
RAM MAPPING ST75C50

CONTENTS		Page
1	INTRODUCTION	1
2	ECHO CANCELLER	2
3	TIMING RECOVERY	2
4	CARRIER RECOVERY	2
5	EQUALIZER, AGC	2
6	HANDSHAKE,RETRAIN,RATE NEGOTIATION	3
7	CARRIER DETECT	4
8	TRANSMIT FILTER COEFICIENTS	5
9	TONE DETECTOR PROGRAMMING	6
10	GENERAL PURPOSE	6
11	TONE GENERATOR	6
12	APPENDIX	7

1 - INTRODUCTION

The purpose of this application note is to explain what are the "interesting internal variables" that can be Read, Written or Modified using the **MR**, **MW**, **CR** commands.

Some of these variables have dedicated commands to modify them, like SETGN for **_TXGAIN** or tone detector. However the whole RAM (even external when using the ST18933) and also the DUAL RAM et internal peripherals can be accessed using the three above mentioned commands.

The address, characteristic (R = read, W = write, R/W = read or write), and function of key data pump variables is listed below by basic modem functional blocks.

Caution : The Mapping of the variables, given in the appendix is only valid for Revision 1.0 of the ST75C50.

There is no guarantee that it will remain exactly the same for further revisions.

RAM MAPPING ST75C50 APPLICATION NOTE

2 - ECHO CANCELLER

- _RTDELAY** (R) Round trip delay in number of bauds
- _EC_STA** (R/W) Echo canceller execution status word. the echo canceller can be frozen in data mode by reading **_EC_STA** and performing a logical or with the value \$0002 before writing to **_EC_STA**. (i.e. other bits must not be changed)
- (PWREST+1)** (R) Residual echo power estimator for determining loss of connection. The ABS() value of this variable will be greater than \$20 to indicate connection loss, otherwise near 0.
- (FRQOFF+3)** (R) Far-end echo frequency offset. $offset = FRQOFF * .0366$ in Hz typically, $FRQOFF = \$1b(27)$ for 1Hz.
- DELTA** (R) Initial far-end echo power after near end echo canceller convergence. This variable can be read in data mode and has the following typical values.
- | | VALUE | POWER |
|--------|-------|--------|
| \$FFF6 | (-10) | - 9dBm |
| \$FFF7 | (- 9) | -12dBm |
| \$0000 | (0) | -39dBm |
| \$000A | (+10) | -69dBm |
- FEECENBL** (R) Far end echo canceller is enabled. \$FFFF = Enabled \$0000 = Disabled (when initial far-end power is less than -69dBm).

3 - TIMING RECOVERY

- (FRQOFF+1)** (R) Receive clock frequency offset.
- PSITHRSH** (R) .94 Deg timing phase adjustment threshold for timing signal dpll.

Comments : The local-to-remote modem timing offset can be calculated using the following formula :

$$TIMING\ OFFSET = \frac{FRQOFF}{PSITHRSH} * \frac{.94}{360}$$

The normal timing offset is within +/- 1.0e-4 for most connections

4 - CARRIER RECOVERY

- (FRQOFF+1)** (R) Receive carrier frequency offset. $OFFSET = FRQOFF * .0366$ in Hz. Typically, $FRQOFF = \$1B(27)$ for 1Hz.

5 - EQUALIZER, AGC

- _RX_STA** (R/W) Equalizer and AGC can be frozen independently or simultaneously.
- ```
%----- X - X
 : :
 : :
 : :1 = freeze equalizer
 : :1 = freeze AGC
```
- = Do not change
- \_RX\_STA** must be modified in data mode and the other bits must be unchanged. Read the value and change only the corresponding bits in the **\_RX\_STA** word.
- (\_AGCSCA+1)** (R/W) Automatic gain control level for receive signal varies from \$80(0dBm) to \$7fff (48dBm).

## RAM MAPPING ST75C50 APPLICATION NOTE

**RDQUA** (R) Equalizer error energy gives an idea of signal to noise ratio seen by the receiver. RDQUA has the following typical values.

| VALUE  | POWER |
|--------|-------|
| \$00C0 | 30 DB |
| \$0180 | 27 DB |
| \$0300 | 24 DB |
| \$0600 | 21 DB |
| \$0C00 | 18 DB |
| \$1800 | 15 DB |
| \$3000 | 12 DB |

**\_RDCPT** (R) Output of Demodulator. Complex number, can be used to display the received eye.

**EQFRK0E** (R/W) 32 Complex even equalizer coefficients.

**EQFRK1E** (R/W) 32 Complex odd equalizer coefficients.

### 6 - HANDSHAKE,RETRAIN,RATE NEGOTIATION

**\_SHSK** (R) Handshake progression counter contains information about the progress of the handshake in v.32 and v.22b modes. It can be read to examine the progression of the handshake and it contains normal values and error values as below:

| V.32 ORIG MODE |                   |                              |
|----------------|-------------------|------------------------------|
| EVENT          | SHSK Normal Value | SHSK Error Value             |
| AC_DET         | \$20              |                              |
| AC/CA DET      | \$21              | \$1                          |
| CA/AC DET      | \$22              | \$2                          |
| NO AC DET      | \$23              | \$B for RTRN, \$C for RRN    |
| S_DET          | \$24              | \$4                          |
| SB_DET         | \$25              | \$5                          |
| R1_DET         | \$26              | \$6                          |
| S_DET          | \$27              | \$7                          |
| SB_DET         | \$28              | \$8                          |
| R3_DET         | \$29              | \$9, \$D no R5 det after RRN |
| E_DET          | \$2A              | \$A                          |
| DATA MODE      | \$30              |                              |

| V.32 ANSW MODE |                   |                             |
|----------------|-------------------|-----------------------------|
| EVENT          | SHSK Normal Value | SHSK Error Value            |
| AA_DET         | \$40              | \$8 for RTRN, \$9 for RRN   |
| AA/CC DET      | \$41              | \$1                         |
| NO CC DET      | \$42              | \$2                         |
| S_DET          | \$43              | \$3                         |
| S_DET2         | \$44              | \$4                         |
| SB_DET         | \$45              | \$5                         |
| R2_DET         | \$46              | \$6, \$A no R det after RRN |
| E_DET          | \$47              | \$7                         |
| DATA MODE      |                   |                             |

| V.22B MODE |                     |
|------------|---------------------|
| EVENT      | SHSK Normal Value   |
| HSK        | \$60 ORIG,\$80 ANSW |
| DATA       | \$70 ORIG,\$90 ANSW |

**\_RE\_HSK** (R) Stored R and E word values which were sent and received in their chronological order during the handshake, retrain, or rate negotiation. Positions **\_RE\_HSK** to **(\_RE\_HSK+4)** contain history during handshake or retrain while **(\_RE\_HSK+5)** to **(\_RE\_HSK+8)** contain history during a rate negotiation request.

## RAM MAPPING ST75C50 APPLICATION NOTE

---

**\_TSPEED** (R/W) Target speed initialized by CONF or RTRA commands but can be changed in data mode for the case of a remote RTRA or RRN requests.

%00000000000000010 = 1200 BPS  
 %00000000000000011 = 2400 BPS  
 %00000000000000100 = 4800 BPS  
 %00000000000000101 = 7200 BPS  
 %00000000000000110 = 9600 BPS  
 %00000000000000111 = 12000 BPS  
 %0000000000001000 = 14400 BPS

**\_TRWORD** (R/W) Target RWORD initialized by CONF or RTRA commands but can be changed (both of them) in data mode for the case of remote RTRA or RRN requests. In reference to the CCITT recommendation the bits are programmed in the following order :

(CCITT RECOMMENDATION)

B00, B01, B02, B03, B04, B05, B06, B07, B08, B09, B10, B11, B12, B13, B14, B15

D15, D14, D13, D12, D11, D10, D09, D08, D07, D06, D05, D04, D03, D02, D01, D00

(\_TRWORD)

**RNTHRSH** (R/W) Threshold for rate negotiation during handshake or retrain. The quality of the receive signal is observed (can be disabled by the command MODC) and the corresponding R word is proposed in the handshake or retrain rate negotiation. The default value is \$300. This gives the typical R word authorization characteristics as shown below:

| SPEED authorized | SNR    |
|------------------|--------|
| 14400            | > 24DB |
| 12000            | < 24DB |
| 9600             | < 21DB |
| 7200             | < 18DB |

Doubling the threshold will decrease the corresponding snr by 3dB approximately.

### 7 - CARRIER DETECT

**DETH1** (R/W) Fast detection threshold  
**DETH** (R/W) Slow detection threshold  
**LOSSTH1** (R/W) Slow loss threshold  
**LOSSTH** (R/W) Fast loss threshold

The carrier detect contains 2 signal level integrators, a fast integrator for quick detection with a limited precision and a slow integrator for enhanced precision. There are four thresholds programmed with default values for each of the modes V.22B, V.33, V.17, FSK, V.29, and V.27 which can be modified by the user after the conf command. Typical values are shown below and doubling the value will increase the threshold by approximately 6dB :

|          |      |                                  |
|----------|------|----------------------------------|
| (-40DBM) | \$B0 | DETH1 (fast detection threshold) |
| (-44DBM) | \$90 | DETH (slow detection threshold)  |
| (-47DBM) | \$60 | LOSSTH1 (slow loss threshold)    |
| (-51DBM) | \$40 | LOSSTH (fast loss threshold)     |

## RAM MAPPING ST75C50 APPLICATION NOTE

### 8 - TRANSMIT FILTER COEFFICIENTS

- TXCOEF** (R/W) Address of first pulse shaping/compromise equalizer complex coefficient (16-bit real,16-bit imag).
- GAIN** (R/W) Attenuation factor for the transmit filter.
- SHIFTVAL** (R/W) Gain (Left shift value) from 0 to 15. To be use in conjunction with GAIN for fine adjustment of the transmit signal. Up and down scaling.

The pass-band pulse shaping and transmit compromise equalizer functions are combined in the transmit filter coefficients. The pulse shaping also performs the multi-phase interpolation from different baud rates to a fixed sample rate 7200Hz (14400Hz for V.27 4800) thus requiring multiple coefficient sub-tables containing complex (16-bit real,16-bit imag) coefficients. The number of coefficients depends on the shape, baud rate, and sampling rate. A default table depending on the compromise equalizer selected in the conf command is loaded from coefficient memory to external memory, after which, if desired, they can be modified by the user. The table below summarizes the location and the number of coefficients to be loaded.

(\* = DEFAULT VALUES)

| MODE             | BAUD RATE | PHASE | COEF/PHS | STRT ADR     | ROLL-OFF* | NO. OF COMPEQ* |
|------------------|-----------|-------|----------|--------------|-----------|----------------|
| V.32/33/17       | 2400      | 0     | 32       | TXCOEF       | 0.125     | 3              |
|                  |           | 1     |          | (TXCOEF+64)  |           |                |
|                  |           | 2     |          | (TXCOEF+128) |           |                |
| V.29             | 2400      | 0     | 24       | TXCOEF       | 0.20      | 2              |
|                  |           | 1     |          | (TXCOEF+48)  |           |                |
|                  |           | 2     |          | (TXCOEF+96)  |           |                |
| V.27(2400)       | 1200      | 0     | 8        | TXCOEF       | 0.50      | 1(FLAT)        |
|                  |           | 1     |          | (TXCOEF+16)  |           |                |
|                  |           | 2     |          | (TXCOEF+32)  |           |                |
|                  |           | 3     |          | (TXCOEF+48)  |           |                |
|                  |           | 4     |          | (TXCOEF+64)  |           |                |
|                  |           | 5     |          | (TXCOEF+80)  |           |                |
| V.27(4800)       | 1600      | 0     | 7        | TXCOEF       | 0.50      | 1(FLAT)        |
|                  |           | 1     |          | (TXCOEF+14)  |           |                |
|                  |           | 2     |          | (TXCOEF+28)  |           |                |
|                  |           | 3     |          | (TXCOEF+42)  |           |                |
|                  |           | 4     |          | (TXCOEF+56)  |           |                |
|                  |           | 5     |          | (TXCOEF+70)  |           |                |
|                  |           | 6     |          | (TXCOEF+84)  |           |                |
|                  |           | 7     |          | (TXCOEF+98)  |           |                |
|                  |           | 8     |          | (TXCOEF+112) |           |                |
| V.22<br>ORIG/ANS | 600       | 0     | 5        | TXCOEF       | 0.50      | 1(FLAT)        |
|                  |           | 1     |          | (TXCOEF+10)  |           |                |
|                  |           | 2     |          | (TXCOEF+20)  |           |                |
|                  |           | 3     |          | (TXCOEF+30)  |           |                |
|                  |           | 4     |          | (TXCOEF+40)  |           |                |
|                  |           | 5     |          | (TXCOEF+50)  |           |                |
|                  |           | 6     |          | (TXCOEF+60)  |           |                |
|                  |           | 7     |          | (TXCOEF+70)  |           |                |
|                  |           | 8     |          | (TXCOEF+80)  |           |                |
|                  |           | 9     |          | (TXCOEF+90)  |           |                |
|                  |           | 10    |          | (TXCOEF+100) |           |                |
|                  |           | 11    |          | (TXCOEF+110) |           |                |

## RAM MAPPING ST75C50 APPLICATION NOTE

---

### 9 - TONE DETECTOR PROGRAMMING

**LEVOUT** (R/W) 16 Programmable static levels.

**BIQCOEF** (R/W) 16\*2\*6 Biquad coefficients.

Coef. order for each of 16 4th order cells :  
C0, C1, C2, C3, C4, C5, C6, C7, C8, C9, CA, CB

Where each 4th order cell has the following xfer function :

$$\frac{OUT}{IN} = C0 \cdot \frac{C5 \cdot Z^2 + 2 \cdot C3 \cdot Z + 2 \cdot C4}{Z^2 - 2 \cdot C1 \cdot Z - 2 \cdot Z} \cdot C6 \cdot \frac{CB \cdot Z^2 + 2 \cdot C9 \cdot Z + 2 \cdot CA}{Z^2 - 2 \cdot C7 \cdot Z - 2 \cdot C8}$$

**POWCOEF** (R/W) 16 Power coefficients p1 Power estimator using absolute value of the input signal :

$$\frac{OUT}{IN} = P1 \cdot \frac{1}{Z - (1 - P1)}$$

**BPWIRE** (R/W) 16 Biquad and pwr estimator input wiring addresses  
FORMAT = [4TH ORDER BIQ(MSB),PWR(LSB)]

**CPWIRE** (R/W) 16 Comparator input wiring addresses  
FORMAT = [COMPARATOR+(MSB),COMPARATOR-(LSB)]

The wiring addresses furnished in bpwire,cpwire are from the following possible sources :

|                                    |              |
|------------------------------------|--------------|
| GND                                | \$00         |
| RX SIGNAL                          | \$01         |
| RX SIGNAL*2                        | \$02         |
| RX SIGNAL*4                        | \$03         |
| 4TH ORDER BIQ BLOCK OUTPUT         | \$10 TO \$1F |
| POWER OUTPUT                       | \$20 TO \$2F |
| STATIC LEVELS PROGRAMMED IN LEVOUT | \$30 TO \$3F |

**\_NTDCELL** (R/W) Number of tone detector cells active (0-15)

**\_TONEDET** (R) Outputs of tone detectors. The low byte of \_TONEDET contains the outputs of tone detector cells 0 to 8. The low byte of \_TONEDET+1 contains outputs of cells 9 to 15. When the corresponding bit is "1" the signal at the positive input of the comparator is higher than that at the negative input. Only \_NTDCELL bits are valid at one time, the other one are 0.

### 10 - GENERAL PURPOSE

**\_TXGAIN** (R/W) Transmit gain. Any signal to transmit is multiplied by this number. This is the value modified by SETGN command.

### 11. TONE GENERATOR

**\_TGNFLG** (R/W) Tone generator flag. Each of the four low bits of this variable define if the corresponding tone generator is enabled. This is the value modified by a TGEN command.

**\_TGOPHC** (R/W) Tone generator #0 phase reversal threshold. If different from 0, a phase reversal will be executed on the tone generator #0 after \_TGOPHC bauds. This is used in V.32 answer tone generation (default value is 1080 for 450ms).

**\_TGNBLK** (R/W) For each of the four tone generators (i) contains:  
\_TGNBLK+(3\*i): Frequency of tone (i.e. \$4000 = 1800Hz).  
\_TGNBLK+1+(3\*i): Instantaneous phase.  
\_TGNBLK+2+(3\*i): Amplitude (\$7FFF refers to maximum signal).

## RAM MAPPING ST75C50 APPLICATION NOTE

### 12 - APPENDIX

#### Address Equivalences for Version 1.0

| Variable                            | Address |
|-------------------------------------|---------|
| ECHO CANCELLER                      |         |
| _RTDELAY                            | \$016   |
| _EC_STA                             | \$019   |
| PWREST                              | \$BAC   |
| FREQOFF                             | \$BAE   |
| DELTA                               | \$BBD   |
| FEECENBL                            | \$BCE   |
| TIMING RECOVERY                     |         |
| FRQOFF                              | \$E8A   |
| PSITHRSH                            | \$E95   |
| CARRIER RECOVERY                    |         |
| FRQOFF                              | \$EA2   |
| EQUALIZER,AGC                       |         |
| _RX_STA                             | \$017   |
| _AGCSCA                             | \$192   |
| RDQUA                               | \$2A7   |
| _RDCPT                              | \$048   |
| EQFRK0E                             | \$CBC   |
| EQFRK1E                             | \$CFC   |
| HANDSHAKE,RETRAIN, RATE NEGOTIATION |         |
| _SHSK                               | \$1BB   |
| _RE_HSK                             | \$1BD   |
| _TSPEED                             | \$1AF   |
| _TRWORD                             | \$1B0   |
| _RWORD                              | \$014   |
| RNTHRSH                             | \$2AA   |

| Variable                     | Address |
|------------------------------|---------|
| CARRIER DETECT               |         |
| DETH1                        | \$F9A   |
| DETH                         | \$F99   |
| LOSSTH1                      | \$F9C   |
| LOSSTH                       | \$F9B   |
| TRANSMIT FILTER COEFFICIENTS |         |
| TXCOEF                       | \$2E4   |
| GAIN                         | \$2E2   |
| SHIFTVAL                     | \$2E1   |
| TONE DETECTOR PROGRAMMING    |         |
| LEVOUT                       | \$3E6   |
| BIQCOEF                      | \$476   |
| POWCOEF                      | \$536   |
| BPWIRE                       | \$456   |
| CPWIRE                       | \$466   |
| _NTDCELL                     | \$006   |
| _TONEDET                     | \$007   |
| GENERAL PURPOSE              |         |
| _TXGAIN                      | \$001   |
| TONE GENERATOR               |         |
| _TGNFLG                      | \$002   |
| _TG0PHC                      | \$003   |
| _TGNBLK                      | \$3A8   |

#### Caution

Add \$1000 to the Addresses when using ST75C50 single chip or ST75C50CIA Kit part.  
Add \$9000 to the Addresses when using Emulation Module.

Information furnished is believed to be accurate and reliable. However, SGS-THOMSON Microelectronics assumes no responsibility for the consequences of use of such information nor for any infringement of patents or other rights of third parties which may result from its use. No licence is granted by implication or otherwise under any patent or patent rights of SGS-THOMSON Microelectronics. Specifications mentioned in this publication are subject to change without notice. This publication supersedes and replaces all information previously supplied. SGS-THOMSON Microelectronics products are not authorized for use as critical components in life support devices or systems without express written approval of SGS-THOMSON Microelectronics.

© 1994 SGS-THOMSON Microelectronics - All Rights Reserved

Purchase of I<sup>2</sup>C Components of SGS-THOMSON Microelectronics, conveys a license under the Philips I<sup>2</sup>C Patent. Rights to use these components in a I<sup>2</sup>C system, is granted provided that the system conforms to the I<sup>2</sup>C Standard Specifications as defined by Philips.

SGS-THOMSON Microelectronics GROUP OF COMPANIES

Australia - Brazil - China - France - Germany - Hong Kong - Italy - Japan - Korea - Malaysia - Malta - Morocco  
The Netherlands - Singapore - Spain - Sweden - Switzerland - Taiwan - Thailand - United Kingdom - U.S.A.