


## Photo Modules for PCM Remote Control Systems

**Special series with short integration time for short burst codes or enhanced data rates**

### Available types for different carrier frequencies

Type	f <sub>0</sub>	Type	f <sub>0</sub>
TFMS 1300	30 kHz	TFMS 1330	33 kHz
TFMS 1360	36 kHz	TFMS 1370	36.7 kHz
TFMS 1380	38 kHz	TFMS 1400	40 kHz
TFMS 1560	56 kHz		



94 8691

### Description


The TFMS 1..0 – series are miniaturized receivers for infrared remote control systems. PIN diode and preamplifier are assembled on lead frame, the epoxy package is designed as IR filter.

The demodulated output signal can directly be decoded by a microprocessor. The main benefit is the reliable function even in disturbed ambient and the protection against uncontrolled output pulses.

### Features

- Receiver module for transmission codes with short bursts ( $N \geq 6$  pulses per bit)
- Photo detector and preamplifier in one package
- Output active low (active high modules: TFMS 1..9)
- Internal filter for PCM frequency
- High immunity against ambient light, optimized against burst noise
- Improved shielding against electric field disturbance
- 5 Volt supply voltage, low power consumption
- TTL and CMOS compatibility
- Low power consumption (typical 2.5 mW)
- 2.4 kbit/s data transmission rate possible  
(N=6, f<sub>0</sub>=56 kHz)

### Block Diagram



94 9148

## Absolute Maximum Ratings

$T_{amb} = 25^\circ C$


Parameter	Test Conditions	Symbol	Value	Unit
Supply Voltage	(Pin 2)	$V_S$	-0.3...6.0	V
Supply Current	(Pin 2)	$I_S$	5	mA
Output Voltage	(Pin 3)	$V_O$	-0.3...6.0	V
Output Current	(Pin 3)	$I_O$	5	mA
Junction Temperature		$T_j$	100	$^\circ C$
Storage Temperature Range		$T_{stg}$	-25...+85	$^\circ C$
Operating Temperature Range		$T_{amb}$	-25...+85	$^\circ C$
Power Consumption	( $T_{amb} \leq 85^\circ C$ )	$P_{tot}$	50	mW
Soldering Temperature	$t \leq 10$ s, 1 mm from case	$T_{sd}$	260	$^\circ C$

## Basic Characteristics

$T_{amb} = 25^\circ C$

Parameter	Test Conditions	Symbol	Min	Typ	Max	Unit
Supply Current (Pin 2)	$V_S = 5 V, E_v = 0$	$I_{SD}$	0.4	0.5	0.8	mA
Supply Current (Pin 2)	$V_S = 5 V, E_v = 40$ klx, sunlight	$I_{SH}$		1.0		mA
Transmission Distance	$E_v = 0$ , Test signal see Fig.7, IR diode TSIP5201, $I_F = 1.5 A$	d		32		m
Output Voltage Low (Pin 3)	$I_{OSL} = 0.5$ mA, $E_e = 0.7$ mW/m <sup>2</sup> , $f = f_o$ , Test signal see Fig.7	$V_{OSL}$			250	mV
Irradiance (30 – 40 kHz)	Test signal see Fig.7	$E_e$ min		0.4	0.6	mW/m <sup>2</sup>
Irradiance (56 kHz)	Test signal see Fig.7	$E_e$ min		0.45	0.7	mW/m <sup>2</sup>
Irradiance	Test signal see Fig.7	$E_e$ max	20			W/m <sup>2</sup>
Directivity	Angle of half transmission distance	$\phi_{1/2}$		$\pm 55$		deg

## Application Circuit



\*) only necessary to suppress power supply disturbances

\*\*) tolerated supply voltage range :  $4.5 V < V_S < 5.5 V$

## Typical Characteristics ( $T_{amb} = 25^{\circ}\text{C}$ unless otherwise specified)




Figure 1 : Frequency Dependence of Responsivity




Figure 2 : Sensitivity in Dark Ambient




Figure 3 : Sensitivity in Bright Ambient




Figure 4 : Sensitivity vs. Electric Field Disturbances




Figure 5 : Sensitivity vs. Supply Voltage Disturbances




Figure 6 : Sensitivity vs. Ambient Temperature

# TFMS 1..0

**TEMIC**

TELEFUNKEN Semiconductors






Figure 7 : Output Function



94 8134




Figure 8 : Output Function




Figure 9 : Sensitivity vs. Duty Cycle




Figure 10 : Output Pulse Diagram




Figure 11 : Supply Current vs. Ambient Temperature




Figure 12 : Spectral Response




Figure 13 : Vertical Directivity  $\phi_y$





Figure 14 : Horizontal Directivity  $\phi_x$

**Dimensions in mm**

**We reserve the right to make changes to improve technical design without further notice.**  
 Parameters can vary in different applications. All operating parameters must be validated for each customer application by the customer. Should the buyer use TEMIC products for any unintended or unauthorized application, the buyer shall indemnify TEMIC against all claims, costs, damages, and expenses, arising out of, directly or indirectly, any claim of personal damage, injury or death associated with such unintended or unauthorized use.

TEMIC TELEFUNKEN microelectronic GmbH, P.O.B. 3535, D-74025 Heilbronn, Germany  
 Telephone: 49 (0)7131 67 2831, Fax Number: 49 (0)7131 67 2423