

EPROM Memory Programming Specification

This document includes the programming specifications for the following devices:

- PIC14C000

1.0 PROGRAMMING THE PIC14C000

The PIC14C000 can be programmed using a serial method. In serial mode the PIC14C000 can be programmed while in the users system. This allows for increased design flexibility. This programming specification applies to PIC14C000 devices in all packages.


1.1 Hardware Requirements

The PIC14C000 requires two programmable power supplies, one for VDD (2.0V to 6.5V recommended) and one for VPP (12V to 14V).

1.2 Programming Mode

The programming mode for the PIC14C000 allows programming of user program memory, configuration word, and calibration memory.

PIN DIAGRAM



PIC14C000

2.0 PROGRAM MODE ENTRY

2.1 User Program Memory Map

The program and calibration memory space extends from 0x0000 to 0xFFFF (4096 words). Table 2-1 shows actual implementation of program memory in the PIC14C000.

TABLE 2-1: IMPLEMENTATION OF PROGRAM AND CALIBRATION MEMORY IN THE PIC14C000P

Area	Memory Space	Access to Memory
Program	0x000-0xFBF	PC<12:0>
Calibration	0xFC0 -0xFFFF	PC<12:0>

When the PC reaches address 0xFFFF, it will wrap around and address a location within the physically implemented memory (see Figure 2-1).

In programming mode the program memory space extends from 0x0000 to 0x3FFF, with the first half (0x0000-0x1FFF) being user program memory and the second half (0x2000-0x3FFF) being configuration memory. The PC will increment from 0x0000 to 0x1FFF and wrap to 0x0000, or 0x2000 to 0x3FFF and wrap around to 0x2000 (not to 0x0000). Once in configuration memory, the highest bit of the PC stays a '1', thus always pointing to the configuration memory. The only way to point to user program memory is to reset the part and reenter program/verify mode, as described in Section 2.2.


In the configuration memory space, 0x2000-0x20FF are utilized. When in configuration memory, as in the user memory, the 0x2000-0x2XFF segment is repeatedly accessed as PC exceeds 0x2XFF (Figure 2-1).

A user may store identification information (ID) in four ID locations. The ID locations are mapped in [0x2000 : 0x2003]. All other locations are reserved and should not be programmed.

The ID locations read out normally, even after code protection. To understand how the devices behave, refer to Table 4-1.

To understand the scrambling mechanism after code protection, refer to Section 4.1.

FIGURE 2-1: PROGRAM MEMORY MAPPING



2.2 Program/Verify Mode

The program/verify mode is entered by holding pins RC6 and RC7 low while raising MCLR pin from V_{IL} to V_{IHH} (high voltage). Once in this mode the user program memory and the configuration memory can be accessed and programmed in serial fashion. The mode of operation is serial, and the memory that is accessed is the user program memory. RC6 and RC7 are both Schmitt Trigger inputs in this mode.

The sequence that enters the device into the programming/verify mode places all other logic into the reset state (the MCLR pin was initially at V_{IL}). This means that all I/O are in the reset state (High impedance inputs).

Note: The MCLR pin should be raised as quickly as possible from V_{IL} to V_{IHH}. This is to ensure that the device does not have the PC incremented while in valid operation range.

2.2.1 PROGRAM/VERIFY OPERATION

The RB6 pin is used as a clock input pin, and the RB7 pin is used for entering command bits and data input/output during serial operation. To input a command, the clock pin (RC6) is cycled six times. Each command bit is latched on the falling edge of the clock with the least significant bit (LSB) of the command being input first. The data on pin RC7 is required to have a minimum setup and hold time (see AC/DC specs) with respect to the falling edge of the clock. Commands that have data associated with them (read and load) are specified to have a minimum delay of 1 μ s between the command and the data. After this delay the clock pin is cycled 16 times with the first cycle being a start bit and the last cycle being a stop bit. Data is also input and output LSB first. Therefore, during a read operation the LSB will be transmitted onto pin RC7 on the rising edge of the second cycle, and during a load operation the LSB will be latched on the falling edge of the second cycle. A minimum 1 μ s delay is also specified between consecutive commands.

TABLE 2-1: COMMAND MAPPING

Command	Mapping (MSB ... LSB)						Data
Load Configuration	0	0	0	0	0	0	0, data(14), 0
Load Data	0	0	0	0	1	0	0, data(14), 0
Read Data	0	0	0	1	0	0	0, data(14), 0
Increment Address	0	0	0	1	1	0	
Begin programming	0	0	1	0	0	0	
End Programming	0	0	1	1	1	0	

Note: The CPU clock must be disabled during in-circuit programming (to avoid incrementing the PC).


All commands are transmitted LSB first. Data words are also transmitted LSB first. The data is transmitted on the rising edge and latched on the falling edge of the clock. To allow for decoding of commands and reversal of data pin configuration, a time separation of at least 1 μ s is required between a command and a data word (or another command).

The commands that are available are listed in Table .

2.2.1.1 LOAD CONFIGURATION


After receiving this command, the program counter (PC) will be set to 0x2000. By then applying 16 cycles to the clock pin, the chip will load 14-bits a "data word" as described above, to be programmed into the configuration memory. A description of the memory mapping schemes for normal operation and configuration mode operation is shown in Figure 2-1. After the configuration memory is entered, the only way to get back to the user program memory is to exit the program/verify test mode by taking $\overline{\text{MCLR}}$ low (V_{IL}).

FIGURE 2-2: PROGRAM FLOW CHART - PIC14C000 PROGRAM MEMORY AND CALIBRATION



PIC14C000

FIGURE 2-3: PROGRAM FLOW CHART - PIC14C000 CONFIGURATION WORD & ID LOCATIONS



2.2.1.2 LOAD DATA

After receiving this command, the chip will load in a 14-bit “data word” when 16 cycles are applied, as described previously. A timing diagram for the load data command is shown in Figure 5-1.

2.2.1.3 READ DATA

After receiving this command, the chip will transmit data bits out of the memory currently accessed starting with the second rising edge of the clock input. The RC7 pin will go into output mode on the second rising clock edge, and it will revert back to input mode (hi-impedance) after the 16th rising edge. A timing diagram of this command is shown in Figure 5-2.

2.2.1.4 INCREMENT ADDRESS

The PC is incremented when this command is received. A timing diagram of this command is shown in Figure 5-3.

2.2.1.5 BEGIN PROGRAMMING

A load command (load configuration or load data) must be given before every begin programming command. Programming of the appropriate memory (test program memory or user program memory) will begin after this command is received and decoded. Programming should be performed with a series of 100 μ s programming pulses. A programming pulse is defined as the time between the begin programming command and the end programming command.

2.2.1.6 END PROGRAMMING

After receiving this command, the chip stops programming the memory (configuration program memory or user program memory) that it was programming at the time.

2.3 Programming Algorithm Requires Variable VDD

The PIC14C000 uses an intelligent algorithm. The algorithm calls for program verification at VDDmin as well as VDDmax. Verification at VDDmin guarantees good “erase margin”. Verification at VDDmax guarantees good “program margin”.

The actual programming must be done with VDD in the VDDP range (4.75 - 5.25V).

VDDP = VCC range required during programming.

VDDmin = minimum operating VDD spec for the part.

VDDmax = maximum operating VDD spec for the part.

Programmers must verify the PIC14C000 at its specified VDDmax and VDDmin levels. Since Microchip may introduce future versions of the PIC14C000 with a broader VDD range, it is best that these levels are user selectable (defaults are ok).


Note: Any programmer not meeting these requirements may only be classified as “prototype” or “development” programmer but not a “production” quality programmer.

PIC14C000

3.0 CONFIGURATION WORD

The PIC14C000 has several configuration bits. These bits can be programmed (reads '0') or left unprogrammed (reads '1') to select various device configurations. Figure 3-1 provides an overview of configuration bits.

FIGURE 3-1: CONFIGURATION WORD BIT MAP



4.0 CODE PROTECTION

The memory space in the PIC14C000 is divided into two areas: program space (0-0xFBF) and calibration space (0xFC0-0xFFF).

For program space or user space, once code protection is enabled, all protected segments read '0's (or "garbage values") and are prevented from further programming. All unprotected segments, including ID locations and configuration word, read normally. These locations can be programmed.

4.1 Calibration Space

The calibration space can contain factory-generated and programmed values. For non-JW devices, the CPC bits in the configuration word are set to '0' at the factory, and the calibration data values are write-protected; they may still be read out, but not programmed. JW devices contain the factory values, but DO NOT have the CPC bits set.

Microchip does not recommend setting code protect bits in windowed devices to '0'. Once code-protected, the device cannot be reprogrammed.

4.1.1 CALIBRATION SPACE CHECKSUM

The data in the calibration space has its own checksum. When properly programmed, the calibration memory will always checksum to 0x0000. When this

checksum is 0x0000, and the checksum of memory [0x0000:0xFBF] is 0x2FBF, the part is effectively blank, and the programmer should indicate such.

If the CPC bits are set to '1', but the checksum of the calibration memory is 0x0000, the programmer should NOT program locations in the calibration memory space, even if requested to do so by the operator. This would be the case for a new JW device.

If the CPC bits are set to '1', and the checksum of the calibration memory is NOT 0x0000, the programmer is allowed to program the calibration space as directed by the operator.

The calibration space contains specially coded data values used for device parameter calibration. The programmer may wish to read these values and display them for the operator's convenience. For further information on these values and their coding, refer to AN621 (DS00621B).

4.1.2 REPROGRAMMING CALIBRATION SPACE

The operator should be allowed to read and store the data in the calibration space, for future reprogramming of the device. This procedure is necessary for reprogramming a windowed device, since the calibration data will be erased along with the rest of the memory. When saving this data, Configuration Word <1,6> must also be saved, and restored when the calibration data is reloaded.

4.2 Embedding Configuration Word and ID Information in the Hex File

To allow portability of code, the programmer is required to read the configuration word and ID locations from the hex file when loading the hex file. If configuration word information was not present in the hex file then a simple warning message may be issued. Similarly, while saving a hex file, configuration word and ID information must be included. An option to not include this information may be provided.

Microchip Technology Inc. feels strongly that this feature is important for the benefit of the end customer.

TABLE 4-1: CODE PROTECT OPTIONS

- Protect calibration memory
0XXXX00XXXXXXX

- Protect program memory
X0000XXX00XXXX
- No code protection
1111111X11XXXX

Program Memory Segment	R/W in Protected Mode	R/W in Unprotected Mode
Configuration Word (0x2007)	Read Unscrambled, Write Enabled	Read Unscrambled, Write Enabled
Unprotected memory segment	Read Unscrambled, Write Enabled	Read Unscrambled, Write Enabled
Protected memory segment	Read All 0's, Write Disabled	Read Unscrambled, Write Enabled
Protected calibration memory	Read Unscrambled, Write Disabled	Read Unscrambled, Write Enabled
ID Locations (0x2000 : 0x2003)	Read Unscrambled, Write Enabled	Read Unscrambled, Write Enabled

Legend: X = Don't care

PIC14C000

4.3 Checksum

4.3.1 CHECKSUM CALCULATIONS

Checksum is calculated by reading the contents of the PIC14C000 memory locations and adding up the opcodes up to the maximum user addressable location, 0xFBF. Any carry bits exceeding 16-bits are neglected. Finally, the configuration word (appropriately masked) is added to the checksum. Checksum computation for the PIC14C000 device is shown in Table 4-2:

The checksum is calculated by summing the following:

- The contents of all program memory locations
- The configuration word, appropriately masked
- Masked ID locations (when applicable)

The least significant 16 bits of this sum is the checksum.

The following table describes how to calculate the checksum for each device. Note that the checksum calculation differs depending on the code protect setting. Since the program memory locations read out differently depending on the code protect setting, the table describes how to manipulate the actual program memory values to simulate the values that would be read from a protected device. When calculating a checksum by reading a device, the entire program memory can simply be read and summed. The configuration word and ID locations can always be read.

Note that some older devices have an additional value added in the checksum. This is to maintain compatibility with older device programmer checksums.

TABLE 4-2: CHECKSUM COMPUTATION

Code Protect	Checksum*	Blank Value	0x25E6 at 0 and max address
OFF	SUM[0000:0FBF] + CFGW & 0x3FBD	0x2FFD	0xFBCB
OFF OTP	SUM[0000:0FBF] + CFGW & 0x3FBD	0x0E7D	0xDA4B
ON	CFGW & 0x3FBD + SUM(IDs)	0x300A	0xFBD8

Legend: CFGW = Configuration Word

SUM[A:B] = [Sum of locations a through b inclusive]

SUM(ID) = ID locations masked by 0x7F then made into a 28-bit value with ID0 as the most significant byte

*Checksum = [Sum of all the individual expressions] MODULO [0xFFFF]

+ = Addition

& = Bitwise AND

5.0 PROGRAM/VERIFY MODE ELECTRICAL CHARACTERISTICS

TABLE 5-1: AC/DC CHARACTERISTICS
AC/DC TIMING REQUIREMENTS FOR PROGRAM/VERIFY MODE

Standard Operating Conditions							
Operating Temperature: $+10^{\circ}\text{C} \leq T_A \leq +40^{\circ}\text{C}$, unless otherwise stated, (25°C recommended)							
Operating Voltage: $4.5\text{V} \leq V_{DD} \leq 5.5\text{V}$, unless otherwise stated.							
Parameter No.	Sym.	Characteristic	Min.	Typ.	Max.	Units	Conditions
General							
PD1	VDDP	Supply voltage during programming	4.75	5.0	5.25	V	
PD2	IDDP	Supply current (from VDD) during programming	–	–	20	mA	
PD3	VDDV	Supply voltage during verify	VDDmin		VDDmax	V	Note 1
PD4	VIHH1	Voltage on MCLR/VPP during programming	12.75	–	13.25	V	Note 2
PD5	VIHH2	Voltage on MCLR/VPP during verify	VDD + 4.0		13.5		
PD6	I _{PP}	Programming supply current (from VPP)	–	–	50	mA	
PD9	VIH1	(RC6, RC7) input high level	0.8 VDD	–	–	V	Schmitt Trigger input
PD8	VIL1	(RC6, RC7) input low level	0.2 VDD	–	–	V	Schmitt Trigger input

Serial Program Verify							
P1	T _R	MCLR/VPP rise time (V _{SS} to V _{HH}) for test mode entry	–	–	8.0	μs	
P2	T _f	MCLR Fall time	–	–	8.0	μs	
P3	T _{set1}	Data in setup time before clock ↓	100	–	–	ns	
P4	T _{hld1}	Data in hold time after clock ↓	100	–	–	ns	
P5	T _{dly1}	Data input not driven to next clock input (delay required between command/data or command/command)	1.0	–	–	μs	
P6	T _{dly2}	Delay between clock ↓ to clock ↑ of next command or data	1.0	–	–	μs	
P7	T _{dly3}	Clock ↑ to data out valid (during read data)	200	–	–	ns	
P8	T _{hld0}	Hold time after MCLR ↑	2	–	–	μs	

Note 1: Program must be verified at the minimum and maximum VDD limits for the part.

Note 2: VIHH must be greater than VDD + 4.5V to stay in programming/verify mode.

PIC14C000

FIGURE 5-1: LOAD DATA COMMAND (PROGRAM/VERIFY)




FIGURE 5-2: READ DATA COMMAND (PROGRAM/VERIFY)





FIGURE 5-3: INCREMENT ADDRESS COMMAND (PROGRAM/VERIFY)



NOTES:



WORLDWIDE SALES AND SERVICE

AMERICAS

Corporate Office

Microchip Technology Inc.
2355 West Chandler Blvd.
Chandler, AZ 85224-6199
Tel: 480-786-7200 Fax: 480-786-7277
Technical Support: 480-786-7627
Web Address: <http://www.microchip.com>

Atlanta

Microchip Technology Inc.
500 Sugar Mill Road, Suite 200B
Atlanta, GA 30350
Tel: 770-640-0034 Fax: 770-640-0307

Boston

Microchip Technology Inc.
5 Mount Royal Avenue
Marlborough, MA 01752
Tel: 508-480-9990 Fax: 508-480-8575

Chicago

Microchip Technology Inc.
333 Pierce Road, Suite 180
Itasca, IL 60143
Tel: 630-285-0071 Fax: 630-285-0075

Dallas

Microchip Technology Inc.
4570 Westgrove Drive, Suite 160
Addison, TX 75248
Tel: 972-818-7423 Fax: 972-818-2924

Dayton

Microchip Technology Inc.
Two Prestige Place, Suite 150
Miamisburg, OH 45342
Tel: 937-291-1654 Fax: 937-291-9175

Detroit

Microchip Technology Inc.
Tri-Atria Office Building
32255 Northwestern Highway, Suite 190
Farmington Hills, MI 48334
Tel: 248-538-2250 Fax: 248-538-2260

Los Angeles

Microchip Technology Inc.
18201 Von Karman, Suite 1090
Irvine, CA 92612
Tel: 949-263-1888 Fax: 949-263-1338

New York

Microchip Technology Inc.
150 Motor Parkway, Suite 202
Hauppauge, NY 11788
Tel: 631-273-5305 Fax: 631-273-5335

San Jose

Microchip Technology Inc.
2107 North First Street, Suite 590
San Jose, CA 95131
Tel: 408-436-7950 Fax: 408-436-7955

AMERICAS (continued)

Toronto

Microchip Technology Inc.
5925 Airport Road, Suite 200
Mississauga, Ontario L4V 1W1, Canada
Tel: 905-405-6279 Fax: 905-405-6253

ASIA/PACIFIC

Hong Kong

Microchip Asia Pacific
Unit 2101, Tower 2
Metroplaza
223 Hing Fong Road
Kwai Fong, N.T., Hong Kong
Tel: 852-2-401-1200 Fax: 852-2-401-3431

Beijing

Microchip Technology, Beijing
Unit 915, 6 Chaoyangmen Bei Dajie
Dong Erhuan Road, Dongcheng District
New China Hong Kong Manhattan Building
Beijing 100027 PRC
Tel: 86-10-85282100 Fax: 86-10-85282104

India

Microchip Technology Inc.
India Liaison Office
No. 6, Legacy, Convent Road
Bangalore 560 025, India
Tel: 91-80-229-0061 Fax: 91-80-229-0062

Japan

Microchip Technology Intl. Inc.
Benex S-1 6F
3-18-20, Shinyokohama
Kohoku-Ku, Yokohama-shi
Kanagawa 222-0033 Japan
Tel: 81-45-471-6166 Fax: 81-45-471-6122

Korea

Microchip Technology Korea
168-1, Youngbo Bldg. 3 Floor
Samsung-Dong, Kangnam-Ku
Seoul, Korea
Tel: 82-2-554-7200 Fax: 82-2-558-5934

Shanghai

Microchip Technology
RM 406 Shanghai Golden Bridge Bldg.
2077 Yan'an Road West, Hong Qiao District
Shanghai, PRC 200335
Tel: 86-21-6275-5700 Fax: 86 21-6275-5060

ASIA/PACIFIC (continued)

Singapore

Microchip Technology Singapore Pte Ltd.
200 Middle Road
#07-02 Prime Centre
Singapore 188980
Tel: 65-334-8870 Fax: 65-334-8850

Taiwan, R.O.C

Microchip Technology Taiwan
10F-1C 207
Tung Hua North Road
Taipei, Taiwan, ROC
Tel: 886-2-2717-7175 Fax: 886-2-2545-0139

EUROPE

United Kingdom

Arizona Microchip Technology Ltd.
505 Eskdale Road
Wokingham
Berkshire, England RG41 5TU
Tel: 44 118 921 5858 Fax: 44-118 921-5835

Denmark

Microchip Technology Denmark ApS
Regus Business Centre
Lautrup hof 1-3
Ballerup DK-2750 Denmark
Tel: 45 4420 9895 Fax: 45 4420 9910

France

Arizona Microchip Technology SARL
Parc d'Activite du Moulin de Massy
43 Rue du Saule Trapu
Batiment A - 1er Etage
91300 Massy, France
Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79


Germany

Arizona Microchip Technology GmbH
Gustav-Heinemann-Ring 125
D-81739 München, Germany
Tel: 49-89-627-144 0 Fax: 49-89-627-144-44

Italy

Arizona Microchip Technology SRL
Centro Direzionale Colleoni
Palazzo Taurus 1 V. Le Colleoni 1
20041 Agrate Brianza
Milan, Italy
Tel: 39-039-65791-1 Fax: 39-039-6899883

11/15/99



Microchip received QS-9000 quality system certification for its worldwide headquarters, design and water fabrication facilities in Chandler and Tempe, Arizona in July 1999. The Company's quality system processes and procedures are QS-9000 compliant for its PICmicro® 8-bit MCUs, KEELOC® code hopping devices, Serial EEPROMs and microperipheral products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001 certified.

All rights reserved. © 1999 Microchip Technology Incorporated. Printed in the USA. 11/99 Printed on recycled paper.

Information contained in this publication regarding device applications and the like is intended for suggestion only and may be superseded by updates. No representation or warranty is given and no liability is assumed by Microchip Technology Incorporated with respect to the accuracy or use of such information, or infringement of patents or other intellectual property rights arising from such use or otherwise. Use of Microchip's products as critical components in life support systems is not authorized except with express written approval by Microchip. No licenses are conveyed, implicitly or otherwise, under any intellectual property rights. The Microchip logo and name are registered trademarks of Microchip Technology Inc. in the U.S.A. and other countries. All rights reserved. All other trademarks mentioned herein are the property of their respective companies.