



3060 RF Combiner PXI Module



Operating Manual

Document no. 46892/640

Issue 7

12 February 2008

About this manual

This manual applies to instruments with software issues of 2.0 and higher.

This manual explains how to set up and configure an Aeroflex 3060 RF combiner PXI module. Where necessary, it refers you to the appropriate installation documents that are supplied with the module.

This manual provides information about how to configure the module as a stand-alone device. However, one of the advantages of Aeroflex 3000 Series PXI modules is their ability to form versatile test instruments, when used with other such modules and running 3000 Series application software.

© Aeroflex International Ltd. 2007

No part of this document may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying, or recorded by any information storage or retrieval system, without permission in writing by Aeroflex International Ltd. (hereafter referred to throughout the document as 'Aeroflex').

Intended audience

Users who need to provide a single combined output from any combination of three input ports, or direct RF switched connection between ports.

This manual is intended for first-time users, to provide familiarity with basic operation. Programming is not covered in this document but is documented fully in the [help files](#) that accompany the drivers and associated software on the CD-ROM.

Driver version

This PXI RF module is designed to be used with the latest software driver version supplied on the Aeroflex 3000 Series PXI Modules CD-ROM part no. 46886/028. Operation with earlier versions of driver software may not be supported.

Structure

| | |
|------------------|-----------------------------|
| Chapter 1 | General information |
| Chapter 2 | Installation |
| Chapter 3 | Operation |
| Chapter 4 | Brief technical description |
| Chapter 5 | Acceptance testing |

Associated documentation

The following documentation covers specific aspects of this equipment:

| | | |
|---|-----------------------|--|
| PXI Modules CD-ROM | Part no. 46886/028 | Compilation containing soft front panels, drivers, application software, data sheets, getting started and operating manuals for this and other modules in the 3000 Series. |
| 3000 Series PXI Modules Common Installation Guide | Part no. 46882/663 | Detailed information on installing modules into a chassis, external connections, powering up and installing drivers. Multilingual safety precautions. |
| 3000 Series PXI Modules Installation Guide for Chassis | Part no. 46882/667 | Explains how to set up a populated chassis ready for use. |
| PXI Studio User Guide | Part no: 46892/809 | Setting up and using the universal PXI application for system configuration and operation. |

Preface

The PXI concept

VXI and GPIB systems meet the specific needs of instrumentation users but are often too large and expensive for mainstream applications. PC-based instrumentation may cost less but cannot meet the environmental and operational requirements of many systems.

PXI (PCI Extensions for Instrumentation) is based on CompactPCI, itself based on the PCI standard. PCI was designed for desktop machines but CompactPCI was designed for industrial applications, and features a rugged Eurocard format with easy insertion and removal. PXI adds to the CompactPCI specification by defining system-level specifications for timing, synchronization, cooling, environmental testing, and software. While PXI extends CompactPCI, it also maintains complete interoperability so that you can use any CompactPCI-compliant product in a PXI system and vice versa. PXI also makes use of Windows software, VXI timing and triggering, and VXIplug&play instrument drivers to provide powerful and affordable systems.

IQCreator® is a registered trademark of Aeroflex International Inc. in the US

PXI™ is a registered trademark of the PXI Systems Alliance

Windows™, Windows XP™ and Windows NT™ are trademarks of Microsoft Corporation

Abbreviations/acronyms

| | |
|-------|--|
| ACP | Adjacent Channel Power |
| AM | Amplitude Modulation |
| CW | Continuous Wave |
| dB | Decibels |
| dBc | Decibels relative to the carrier level |
| dBm | Decibels relative to 1 mW |
| FM | Frequency Modulation |
| GND | Ground |
| LO | Local Oscillator |
| MSA | Microwave Scalar Analyzer |
| PCI | Peripheral Component Interconnect |
| Pk-Pk | Peak-to-Peak |
| PXI | PCI eXtensions for Instrumentation |
| RF | Radio Frequency |
| RMS | Root Mean Square |
| SFP | Soft Front Panel |
| SMA | SubMiniature version A (connector) |
| UUT | Unit Under Test |
| VSWR | Voltage Standing-Wave Ratio |
| VXI | VMEbus Extension for Instrumentation |

Chapter 1 GENERAL INFORMATION



Introduction


Welcome to the operating manual for the 3060 RF combiner PXI module. This high-performance three-input combiner covers the frequency range 300 MHz to 2.5 GHz, using a 3U high single-slot module.

This module is intended for use in RF test systems with the 3020 Series digital RF signal generator and 3030 Series RF digitizer. Together, these modules enable compact, high performance modular RF test systems to be developed.

GENERAL INFORMATION

The 3060 combiner has two modes of operation:

- In its normal mode, it provides a single combined output from any combination of three input ports. Each port is bi-directional, allowing many system configurations.
- In its calibration mode, it provides direct RF switched connection between ports A and B, and B and C, to enable automated test system calibration.



The 3060 stores its own path loss calibration data, which can be accessed via software calls to the driver.

Applications

The 3060 can be used in radio test applications such as transceiver testing, where the combined port Σ acts as a single port duplex connection, one or two RF sources provide TX stimulus inputs, and an RF signal analysis instrument connected to the third port measures the DUT's TX parameters.

Software

The 3060 is supplied with a VXI PNP driver and soft front panel, and a dll and COM object that provide similar functionality to the driver.

PXI Studio, supplied with the module, configures your PXI modules as logical instruments using an intuitive and powerful graphical interface. Currently, PXI Studio provides comprehensive signal generator, digitizer and spectrum analyzer applications and further development will provide analysis plugins to suit any modulation scheme.

RF Investigator, also supplied with the module, is an application that provides combined operation of all Aeroflex 3000 Series modules from a single user interface, especially useful for acceptance testing.

Deliverable items

- 3060 RF Combiner PXI module
- PXI Modules CD-ROM part no. 46886/028, containing soft front panels, drivers, application software, data sheets, getting started and operating manuals for this and other modules in the 3000 Series
- *3000 Series PXI Modules Common Installation Guide*, part no. 46882/663
- *3000 Series PXI Modules Installation Guide for Chassis*, part no. 46882/667
- SMA connector cable, part no. 43139/590, 2 off
- 50 ohm termination SMA, part no. 82532

Cleaning

Before commencing any cleaning, switch off the chassis and disconnect it from the supply. You can wipe the front panel of the module using a soft cloth moistened in water, taking care not to wet the connectors. Do not use aerosol or liquid solvent cleaners.

Putting into storage

If you put the module into storage, ensure that the following conditions are not exceeded:

Temperature range: -20 to $+70^{\circ}\text{C}$ (-4 to $+158^{\circ}\text{F}$)

Humidity: 5 to 93%, non-condensing

Chapter 2 INSTALLATION

WARNING

Initial visual inspection

Refer to the 3000 Series Common Installation Guide 46882/663.

CAUTION

Handling precautions

Refer to the 3000 Series Common Installation Guide 46882/663.

Hardware installation

Installing the module into the PXI chassis

Refer to the 3000 Series Common Installation Guide 46882/663 and Installation Guide for Chassis 46882/667.

Connector care and maintenance

How to connect and torque an SMA connector

- 1 First, ensure that the mating halves of the connector are correctly aligned.
- 2 Next, engage the threads of the nut and tighten it by hand, ensuring that the mating halves do not move relative to each other.
- 3 Then use a torque spanner to tighten the connector, in order to ensure consistent matching and to avoid mechanical stress.

Torque settings for connectors are:

0.56 Nm test torque (development use, semi-permanent installations)

1 Nm final torque (permanent installations)

Never use pliers to tighten connectors.

Maintenance

SMA

Clean connectors regularly, using a cotton bud dipped in isopropyl alcohol. Wipe within the connector cavity, then use a dry cotton bud to finish off. Check for any deposits.

Do not use other cleaners, as they can cause damage to the plastic insulators within the connectors.


Cap unused connectors.

PCI

Protect PCI connector pins by keeping modules in their original packing when not fitted in the rack.

Chapter 3 OPERATION

Front-panel connectors



- | | | |
|---|----------|--|
| 1 | Σ | Combined output. SMA socket, 50 Ω . |
| 2 | A, B, C | Individual inputs. SMA socket, 50 Ω . |

CAUTION

Maximum safe powers

Σ port: **+27 dBm**, 3 V dc

A, B, C ports: **+17 dBm**

Fig. 3-1 3060 front panel

Soft front panel (af3060_sfp)

The soft front panel provides a graphical interface for operating the module. It is intended for testing and diagnosing, for demonstration and training, and for basic operation of the module. It represents most of the functions available in the instrument driver. It is not however a comprehensive application suitable for measurements: for this, use the appropriate driver, COM object or C interface DLL, supplied with the modules that form the test system.


Installation

The soft front panel is installed during the driver installation process (refer to the 3000 Series PXI Modules Common Installation Guide part no. 46882/663).

Open the *AF3060_sfp.exe* file; this is in the *C:\VXIPNP\WinNT\af3060* directory on a Windows NT machine, for example. It is also accessible from the Windows Start menu under *Programs\Aeroflex\PXI Module Front Panels\AF3060 Front Panel*. The soft front panel, similar to that in Fig. 3-2, is displayed.

Detailed help information

Soft front panel controls are all available as [driver export functions](#) unless noted otherwise, and are documented in the [help files](#) (page 3-6). This operating manual provides an overview of the facilities that the module provides and summarizes its operation; however, refer to the help files for detailed descriptions of functions, together with their parameter lists and return values.



C5982

Fig. 3-2 Combiner soft front panel

Soft front panel controls

Menu bar

File

Click **Exit** to close the application.

Settings

Load and **Save** allow you to load and save soft front panel configurations from and to your preferred locations. If you did not change the default location when installing the software, it is *C:\VXIPNP\WinNT\af3060\settings*, and settings are saved as *.ini* files.

You can edit settings files as required. Edit the saved *.ini* file using a text editor (for example, Notepad) to remove unwanted parameters. Ensure only that you do not delete the General (VendorID, DeviceID) and Version (Major/Minor) parameters. Save the changed file. When the settings file is next loaded, the configuration of the soft front panel changes to match the parameters remaining in the settings file.

Directories lets you choose the locations for your front-panel configuration settings.

Options

There are no options available on the 3060.

Help

Instrument Information provides the module's PXI resource code and serial number, revision numbers for driver and PCI, its last calibration date, and associated file information and module build information.

About provides the version and date of the soft front panel.

Boot

Click **Boot** to initialize the module and view the Boot Resource window. Resources available for initializing are shown in blue.

Select the 3060. Click **OK**. While you select the boot resource, the indicator is amber. Once the module has initialized, the indicator changes to green in a few seconds.

If no calibration data is available, the driver returns a caution. If this happens, return the module for calibration.

s/n:

After the module initializes, this field displays its serial number.

Res:

After the module initializes, this field displays its VISA resource string.

Switching

Combiner Switching

Check ABC via Combiner to provide a single combined output at Σ from all of the inputs A, B and C. All ports are bi-directional.

Check A to B or B to C to provide direct RF connections. Unswitched ports remain routed to Σ .

Combiner Loss

Displays the losses, in dB, of various combiner paths at the frequency entered in the RF Frequency (Hz) field. For example, A to Sum (dB) displays the dB loss between the A and Σ ports at the specified frequency.

Driver export functions

On-line help and functional documentation for driver export functions are available on the CD-ROM supplied with your module. They are installed onto your computer at the same time as the drivers.

Driver installation folder

Find help and functional documentation in the driver installation folder on your computer.

This is typically:

C:\vxiinp\winnt\af3060

Help

Within the driver installation folder are help files that provide descriptions, parameter lists and return values. Help files are provided in three formats:

| | | |
|---------------------|--------------------------------------|----------------------------|
| <i>af3060.doc</i> | 3060 function documentation | Text file |
| <i>af3060.hlp</i> | 3060 Visual BASIC function reference | } Windows Help file format |
| <i>af3060_C.hlp</i> | 3060 C language function reference | |

We recommend that you use the C or Visual Basic formats as these are easier to navigate.

The file opens at the Contents page:




Fig. 3-3 Online help contents — example

Hyperlinks from here take you to

Introduction

Assumptions

Error codes

Functions listings.

Functions listings

Functions are grouped by type. Click on the hyperlink for details of the function. Each function has a description of its purpose, and may have a list of parameters and return values.




Fig. 3-4 Function description — example

Chapter 4 BRIEF TECHNICAL DESCRIPTION

Introduction

The 3060 is a high performance three-input RF combiner covering the frequency range 250 MHz to 2.5 GHz, usable to 3.0 GHz. It is supplied as a single-slot 3U PXI module. A [block schematic](#) for the instrument is shown in Fig. 4-1.

The combiner operates in two modes: combination and calibration.

Combination

The combiner provides a single combined output at port \square from any combination of signals on input ports A, B and C; with a nominal insertion loss of <15 dB. Each port is bi-directional, allowing a variety of system configurations.

Calibration

The combiner provides direct RF switched connection between ports A and B, and C and B, to allow automated test system calibration. In this mode the path loss is <2 dB.

Electronic RF switching is used to ensure that minimal time delays are incurred when performing system calibration, as well as providing high reliability for volume manufacturing. RF switch control and combiner path calibration information is communicated via the PXI backplane.

The 3060 module consists of a RF block and a PCI interface board; a description of each is given below.

RF block

The RF block performs the signal combination and switching between ports A, B, C and Σ . Port switching is implemented using PIN diodes and the combiner is implemented using passive high isolation balun technology.

When the combination mode is selected, forward-biased diodes allow RF signals on ports A, B and C to reach their respective combining circuitry based around two transformer baluns, and then to the output port Σ . A chain of diodes achieves the required port-to-port isolation.

When 'A to B' is selected, diode switches connect port A to port B and isolates these ports from the combiner circuitry. The match looking into port Σ is maintained. Port C is not affected when 'A to B' calibration mode is selected. A similar process occurs when mode 'C to B' is selected.

PCI interface

The PCI interface enables inter-module communication via the PCI bus and provides control and power signals to the 3060. An EEPROM is used to store module related calibration data.

BRIEF TECHNICAL DESCRIPTION




Fig. 4-1 Block schematic diagram

Chapter 5 ACCEPTANCE TESTING

Introduction

The test procedures in this chapter enable you to verify that the 3060 RF Combiner is meeting its specified performance.

Abbreviations

Throughout the chapter, the following abbreviations are used:

UUT Unit Under Test
SFP Soft Front Panel

Test procedures

Each test procedure shows you how to configure the test equipment and then describes how to perform the test. Tables are provided for recording your results. Measurements should fall within the maximum and minimum limits indicated, provided that you use the recommended test equipment and adhere to the [test precautions](#).

The tests recommend the use of conventional ‘rack and stack’ test equipment. Other PXI modules may be used as long as they comply with the minimum specification.

Controlling the UUT

Control of the UUT is by the SFP supplied on the CD-ROM (part no. 46886/028).

Follow the instructions provided in the 3000 Series Common Installation Guide (part no. 46882/663) to ensure that this software is correctly installed.

ACCEPTANCE TESTING

Each test procedure relies on the module being set to its power-up conditions. To avoid switching the instrument off and back on, reboot the module via the SFP as follows:

- Click on **Boot**.
- Select the appropriate resource from the list.
- Click on **OK**.
- After a few seconds, the indicator turns green to show that the boot sequence has completed successfully.

Note that for clarity, the PXI chassis and controller are not shown in the test equipment setup diagrams.

Recommended test equipment

The test equipment recommended is shown below. Alternative equipment may be used provided it complies with the stated minimum specification. The minimum specification is only an indication of the required performance. With all measurements, you should ensure that the performance of the test equipment has adequate stand-off from the specification of the UUT.

| Description | Minimum specification | Example | Test parameters |
|--------------------------------|-----------------------|-----------------------------|-----------------|
| Signal generator | 250 MHz to 3 GHz | Aeroflex 3413 | Insertion loss |
| Power meter and sensor | 250 MHz to 3 GHz | Aeroflex 6960B and 6924 | Insertion loss |
| Power splitter | 3 GHz | Agilent 11667B | Insertion loss |
| Spectrum analyzer | 3 GHz | Aeroflex 2399B | Isolation |
| Microwave scalar analyzer | 250 MHz to 3 GHz | Aeroflex 6821, 6822 or 6823 | Return loss |
| Autotester | 250 MHz to 3 GHz | Aeroflex 59999/168 | Return loss |
| 50 ohm SMA termination (3 off) | 250 MHz to 3 GHz | Aeroflex 82532 | All |

Test precautions

To ensure minimum errors and uncertainties when making measurements, it is important to observe the following precautions:

- Always use recently calibrated test equipment, with any correction figures taken into account, so as to establish a known traceable limit of performance uncertainty. This uncertainty must be allowed for in determining the accuracy of measurements.
- Ensure any user calibration routines are performed when necessary. On most power meters it is also necessary to perform an auto-zero routine.
- Use the shortest possible connecting leads.
- Allow 20 minutes for the UUT to warm up, plus any extra time for other test equipment being used.

Checking that the UUT powers up correctly

This test ensures that the 3060 powers up in a satisfactory manner and that the internal self-tests do not report any errors. This test assumes that instrument is fitted in a PXI chassis and that the supplied installation software is installed on the host controller.

- Apply power to the PXI chassis.
- Press the supply switch on the PXI chassis.

Wait for the operating system to complete its boot-up sequence.

- Double-click on the af3060_SFP icon.

The 3060 SFP now starts up. After completing its boot-up sequence, the indicator next to the **Boot** button should be red.

- Click on **Boot**.


While the module is booting, the indicator turns amber.

- After a few seconds, the indicator turns green to show that the boot sequence has completed successfully.

Insertion loss and isolation

This test measures the following:

- the loss between the ports A, B, C and the combined port
- the loss between the A and B or B and C ports
- the isolation between ports A and B, A and C, or B and C with the UUT set to ABC via Combiner.



C5946

Fig. 5-1 Insertion loss test set-up

Insertion loss

A-Σ

- 1 Connect the test equipment as shown in Fig. 5-1 and terminate the unused ports with 50 ohm terminations.
- 2 On the UUT set:
ABC via Combiner
- 3 On the signal generator set:
Carrier Frequency 250 MHz
RF Level 0 dBm
- 4 Record the difference in the level measured between power meter 1 and power meter 2 in Table 5-1.
- 5 Repeat (3) and (4) at the remaining frequencies in Table 5-1.

B-Σ

- 6 Connect the signal generator/splitter/power meter 1 to the UUT B port and terminate the unused ports with 50 ohm terminations.
- 7 Repeat (3) and (4) at the remaining frequencies in Table 5-1.

C-Σ

- 8 Connect the signal generator/splitter/power meter 1 to the UUT C port and terminate the unused ports with 50 ohm terminations.
- 9 Repeat (3) and (4) at the remaining frequencies in Table 5-1.

A–B

- 10 Connect the signal generator/splitter/power meter 1 to the UUT A port and power meter 2 to the UUT B port and terminate the unused ports with 50 ohm terminations.
- 11 On the UUT set:
A to B
- 12 Repeat (3) and (4) at the frequencies shown in Table 5-2.

B–C

- 13 Connect the signal generator/splitter/power meter 1 to the UUT B port and power meter 2 to the UUT C port and terminate the unused ports with 50 ohm terminations.
- 14 On the UUT set:
B to C
- 15 Repeat (3) and (4) at the frequencies shown in Table 5-2.

ACCEPTANCE TESTING


Table 5-1 Insertion loss results

| Frequency (MHz) | A- Σ result (dB) | B- Σ result (dB) | C- Σ result (dB) | Limit (dB) |
|-----------------|-------------------------|-------------------------|-------------------------|------------|
| 250 | | | | <15 |
| 500 | | | | <15 |
| 750 | | | | <15 |
| 1000 | | | | <15 |
| 1250 | | | | <15 |
| 1500 | | | | <15 |
| 1750 | | | | <15 |
| 2000 | | | | <15 |
| 2250 | | | | <15 |
| 2500 | | | | <15 |
| 2700 | | | | <16 |

Table 5-2 Insertion loss results

| Frequency (MHz) | A-B result (dB) | B-C result (dB) | Limit (dB) |
|-----------------|-----------------|-----------------|------------|
| 250 | | | <2 |
| 500 | | | <2 |
| 750 | | | <2 |
| 1000 | | | <2 |
| 1250 | | | <2 |
| 1500 | | | <2 |
| 1750 | | | <2 |
| 2000 | | | <2 |
| 2250 | | | <2 |
| 2500 | | | <2 |
| 2700 | | | <3 |

Isolation



C5947

Fig. 5-2 Isolation test setup

A-B

- 1 Connect the test equipment as shown in Fig. 5-2 and terminate all unused ports with 50 ohm terminations.
- 2 On the UUT set:
ABC via Combiner

ACCEPTANCE TESTING

- 3 On the signal generator set:

| | |
|-------------------|---------|
| Carrier Frequency | 250 MHz |
| RF Level | 0 dBm |
- 4 On the spectrum analyzer set:

| | |
|-------------------|---------|
| Carrier Frequency | 250 MHz |
| Ref Level | 0 dBm |
| Span | 100 kHz |
| Marker | ⇒ Peak |
- 5 Record the difference in the level measured between the power meter and the marker on the spectrum analyzer in Table 5-3.
- 6 Repeat (3) to (5) at the remaining frequencies in Table 5-3.

A–C

- 6 Connect the spectrum analyzer to the UUT C port and move the 50 ohm termination to the B port.
- 7 Repeat (3) to (5) at the remaining frequencies in Table 5-3.

B–C


- 8 Connect the signal generator/splitter/power meter to the UUT B port and move the 50 ohm termination to the A port.
- 9 Repeat (3) to (5) at the remaining frequencies in Table 5-3.

ACCEPTANCE TESTING

Table 5-3 Isolation results

| Frequency (MHz) | A-B result (dB) | A-C result (dB) | B-C result (dB) | Limit (dB) |
|-----------------|-----------------|-----------------|-----------------|------------|
| 250 | | | | >35 |
| 500 | | | | >35 |
| 750 | | | | >35 |
| 1000 | | | | >35 |
| 1250 | | | | >35 |
| 1500 | | | | >35 |
| 1750 | | | | >35 |
| 2000 | | | | >35 |
| 2250 | | | | >35 |
| 2500 | | | | >35 |
| 2700 | | | | >35 |

Return loss



C6170

Fig. 5-3 RF input VSWR test setup

Port Σ

- 1 Connect the test equipment as shown in Fig. 5-3 and terminate the unused ports with 50 ohm terminations. Connections to the test port of the autotester are specified during the procedure.
- 2 On the UUT set:
ABC via Combiner
- 3 On the microwave scalar analyzer (MSA) define the source conditions as follows:
[PRESET]
[Full]
[SOURCE]
[Set Start Frequency] 250 [Mu]
[Set Stop Frequency] 2700 [Mu]
- 4 Calibrate the MSA for VSWR measurements as follows:
[CAL]
[Short AND Open Cal]
- 5 Connect the short circuit to the test port of the autotester.
- 6 On the MSA select *[Continue]*
- 7 Remove the short circuit and connect the open circuit to the test port of the autotester.
- 8 On the MSA select *[Continue]*
- 9 Remove the open circuit and connect the test port of the autotester directly to the Σ port on the UUT.
- 10 On the MSA select:
[FORMAT/SCALING]
[VSWR]
Using the rotary control on the MSA, measure the worst case return loss and record the frequency and value in Table 5-4.

Port A

- 11 Connect the autotester to the A port, terminate the unused ports with 50 ohm terminations and repeat (10) above using Table 5-5.

Port B

- 12 Connect the autotester to the B port, terminate the unused ports with 50 ohm terminations and repeat (10) above using Table 5-6.

Port C

- 13 Connect the autotester to the C port, terminate the unused ports with 50 ohm terminations and repeat (10) above using Table 5-7.

Table 5-4 Port Σ return loss result

| Frequency (MHz) | Σ Result (dB) | Limit (dB) |
|-----------------|----------------------|------------|
| | | >20 dB |

Table 5-5 Port A return loss result

| Frequency (MHz) | A Result (dB) | Limit (dB) |
|-----------------|---------------|------------|
| | | >16 dB |

ACCEPTANCE TESTING

Table 5-6 Port B return loss result

| Frequency (MHz) | B Result (dB) | Limit (dB) |
|-----------------|---------------|------------|
| | | >16 dB |

Table 5-7 Port C return loss result

| Frequency (MHz) | C Result (dB) | Limit (dB) |
|-----------------|---------------|------------|
| | | >16 dB |

AEROFLEX INTERNATIONAL LTD. SOFTWARE LICENCE AND WARRANTY

This document is an Agreement between the user of this Licensed Software, the Licensee, and Aeroflex International Limited, the Licensor. By opening this Software package or commencing to use the software you accept the terms of this Agreement. If you do not agree to the terms of this Agreement please return the Software package unopened to Aeroflex International Limited or do not use the software.

1. DEFINITIONS

The following expressions will have the meanings set out below for the purposes of this Agreement:

| | |
|-------------------------------|--|
| Add-In Application Software | Licensed Software that may be loaded separately from time to time into the Equipment to improve or modify its functionality |
| Computer Application Software | Licensed Software supplied to run on a standard PC or workstation |
| Designated Equipment | the single piece of Equipment upon which the licensed software is installed |
| Downloaded Software | any software downloaded from an Aeroflex web site |
| Embedded Software | Licensed Software that forms part of the Equipment supplied by Aeroflex and without which the Equipment cannot function |
| Licence Fee | the consideration ruling at the date of this Agreement for the use of one copy of the Licensed Software on the Designated Equipment |
| Licensed Software | All and any programs, listings, flow charts and instructions in whole or in part including Add-in, Computer Application, Downloaded and Embedded Software supplied to work with Designated Equipment |

2. LICENCE FEE

The Licensee shall pay the Licence Fee to Aeroflex in accordance with the terms of the contract between the Licensee and Aeroflex.

3. TERM

This Agreement shall be effective from the date hereof and shall continue in force until terminated under the provisions of Clause 9.

4. LICENCE

- 4.1 Unless and until terminated, this Licence confers upon the Licensee the non-transferable and non-exclusive right to use the Licensed Software on the Designated Equipment.
- 4.2 The Licensee may not use the Licensed Software on other than the Designated Equipment, unless written permission is first obtained from Aeroflex and until the appropriate additional Licence Fee has been paid to Aeroflex.
- 4.3 The Licensee may not amend or alter the Licensed Software and shall have no right or licence other than that stipulated herein.

- 4.4 The Licensee may make not more than two copies of the Licensed Software (but not the Authoring and Language Manuals) in machine-readable form for operational security and shall ensure that all such copies include Aeroflex's copyright notice, together with any features which disclose the name of the Licensed Software and the Licensee. Furthermore, the Licensee shall not permit the Licensed Software or any part to be disclosed in any form to any third party and shall maintain the Licensed Software in secure premises to prevent any unauthorised disclosure. The Licensee shall notify Aeroflex immediately if the Licensee has knowledge that any unlicensed party possesses the Licensed Software. The Licensee's obligation to maintain confidentiality shall cease when the Licensed Software and all copies have been destroyed or returned. The copyright in the Licensed Software shall remain with Aeroflex. The Licensee will permit Aeroflex at all reasonable times to audit the use of the Licensed Software.
- 4.5 The Licensee will not disassemble or reverse engineer the Licensed Software, nor sub-licence, lease, rent or part with possession or otherwise transfer the whole or any part of the Licensed Software.

5 WARRANTY

- 5.1 Aeroflex certifies that the Licensed Software supplied by Aeroflex will at the time of delivery function substantially in accordance with the applicable Software Product Descriptions, Data Sheets or Product Specifications published by Aeroflex.
- 5.2 The warranty period (unless an extended warranty for Embedded Software has been purchased) from date of delivery in respect of each type of Licensed Software is:
- | | |
|-------------------------------|-------------|
| Embedded Software | 12 months |
| Add-In Application Software | 90 days |
| Computer Application Software | 90 days |
| Downloaded Software | No warranty |
- 5.3 If during the appropriate Warranty Period the Licensed Software does not conform substantially to the Software Product Descriptions, Data Sheets or Product Specifications Aeroflex will provide:
- 5.3.1 In the case of Embedded Software and at Aeroflex's discretion either a fix for the problem or an effective and efficient work-around.
- 5.3.2 In the case of Add-In Application Software and Computer Application Software and at Aeroflex's discretion replacement of the software or a fix for the problem or an effective and efficient work-around.
- 5.4 Aeroflex does not warrant that the operation of any software will be uninterrupted or error free.
- 6 The above Warranty does not apply to:
- 6.1 Defects resulting from software not supplied by Aeroflex, from unauthorised modification or misuse or from operation outside of the specification.
- 6.2 Third party produced Proprietary Software which Aeroflex may deliver with its products, in such case the third party Software Licence Agreement including its warranty terms shall apply.
- 7 The remedies offered above are sole and exclusive remedies and to the extent permitted by applicable law are in lieu of any implied conditions, guarantees or warranties whatsoever and whether statutory or otherwise as to the software all of which are hereby expressly excluded.

8. INDEMNITY

- 8.1 Aeroflex shall defend, at its expense, any action brought against the Licensee alleging that the Licensed Software infringes any patent, registered design, trademark or copyright, and shall pay all Licensor's costs and damages finally awarded up to an aggregate equivalent to the Licence fee provided the Licensee shall not have done or permitted to be done anything which may have been or become any such infringement and shall have exercised reasonable care in protecting the same failing which the Licensee shall indemnify Aeroflex against all claims costs and damages incurred and that Aeroflex is given prompt written notice of such claim and given information, reasonable assistance and sole authority to defend or settle such claim on behalf of the Licensee. In the defence or settlement of any such claim, Aeroflex may obtain for the Licensee the right to continue using the Licensed Software or replace it or modify it so that it becomes non-infringing.
- 8.2 Aeroflex shall not be liable if the alleged infringement:
- 8.2.1 is based upon the use of the Licensed Software in combination with other software not furnished by Aeroflex, or
 - 8.2.2 is based upon the use of the Licensed Software alone or in combination with other software in equipment not functionally identical to the Designated Equipment, or
 - 8.2.3 arises as a result of Aeroflex having followed a properly authorised design or instruction of the Licensee, or
 - 8.2.4 arises out of the use of the Licensed Software in a country other than the one disclosed to Aeroflex as the intended country of use of the Licensed Software at the commencement of this Agreement.
- 8.3 Aeroflex shall not be liable to the Licensee for any loss of use or for loss of profits or of contracts arising directly or indirectly out of any such infringement of patent, registered design, trademark or copyright.

9. TERMINATION

- 9.1 Notwithstanding anything herein to the contrary, this Licence shall forthwith determine if the Licensee:
- 9.1.1 As an individual has a Receiving Order made against him or is adjudicated bankrupt or compounds with creditors or as a corporate body, compounds with creditors or has a winding-up order made against it or
 - 9.1.2 Parts with possession of the Designated Equipment.
- 9.2 This Licence may be terminated by notice in writing to the Licensee if the Licensee shall be in breach of any of its obligations hereunder and continue in such breach for a period of 21 days after notice thereof has been served on the Licensee.
- 9.3 On termination of this Agreement for any reason, Aeroflex may require the Licensee to return to Aeroflex all copies of the Licensed Software in the custody of the Licensee and the Licensee shall, at its own cost and expense, comply with such requirement within 14 days and shall, at the same time, certify to Aeroflex in writing that all copies of the Licensed Software in whatever form have been obliterated from the Designated Equipment.

10. THIRD PARTY LICENCES

The software or part thereof may be the proprietary property of third party licensors. In such an event such third party licensors (as referenced on the package or the Order Acknowledgement) and/or Aeroflex may directly enforce the terms of this Agreement and may terminate the Agreement if the Licensee is in breach of the conditions contained herein.

11. EXPORT REGULATIONS

The Licensee undertakes that where necessary the Licensee will conform with all relevant export regulations imposed by the Governments of the United Kingdom and/or the United State of America.

12. NOTICES

Any notice to be given by the Licensee to Aeroflex shall be addressed to:

Aeroflex International Limited, Longacres House, Six Hills Way, Stevenage, SG1 2AN, UK.

13. LAW AND JURISDICTION

This Agreement shall be governed by the laws of England and shall be subject to the exclusive jurisdiction of the English courts. This agreement constitutes the whole Contract between the parties and may be changed only by memorandum signed by both parties.

© AEROFLEX INTERNATIONAL LTD 2007

**CHINA Beijing**

Tel: [+86] (10) 6539 1166

Fax: [+86] (10) 6539 1778

CHINA Shanghai

Tel: [+86] (21) 5109 5128

Fax: [+86] (21) 5150 6112

FINLAND

Tel: [+358] (9) 2709 5541

Fax: [+358] (9) 804 2441

FRANCE

Tel: [+33] 1 60 79 96 00

Fax: [+33] 1 60 77 69 22

GERMANY

Tel: [+49] 8131 2926-0

Fax: [+49] 8131 2926-130

HONG KONG

Tel: [+852] 2832 7988

Fax: [+852] 2834 5364

INDIA

Tel: [+91] 80 5115 4501

Fax: [+91] 80 5115 4502

KOREA

Tel: [+82] (2) 3424 2719

Fax: [+82] (2) 3424 8620

SCANDINAVIA

Tel: [+45] 9614 0045

Fax: [+45] 9614 0047

SPAIN

Tel: [+34] (91) 640 11 34

Fax: [+34] (91) 640 06 40

UK Burnham

Tel: [+44] (0) 1628 604455

Fax: [+44] (0) 1628 662017

UK Stevenage

Tel: [+44] (0) 1438 742200

Fax: [+44] (0) 1438 727601

Freephone: 0800 282388

USA

Tel: [+1] (316) 522 4981

Fax: [+1] (316) 522 1360

Toll Free: (800) 835 2352

As we are always seeking to improve our products, the information in this document gives only a general indication of the product capacity, performance and suitability, none of which shall form part of any contract. We reserve the right to make design changes without notice.

web www.aeroflex.comEmail info-test@aeroflex.comNovember 2005
