

IBM 8265

Nways ATM Switch

**This release note applies to
ATM Control Point version V4.1.0
PNNI and IISP**

PN 03N0367 Page 1 of 11	EC F52346A 1March1999				
----------------------------	--------------------------	--	--	--	--

This document is the property of IBM. Its use is authorized only for responding to a request for quotation or for the performance of work for IBM. All questions must be referred to the IBM purchasing department.

Table of Contents

1•Warnings	3
2•New Features	4
3•Fixes	5
4•Known Problems	6
5•MIB V4	7
6•8265 Modules FPGA Levels	8

PN 03N0367 Page 2 of 11	EC F52346A 1March1999				
----------------------------	--------------------------	--	--	--	--

This document is the property of IBM. Its use is authorized only for responding to a request for quotation or for the performance of work for IBM. All questions must be referred to the IBM purchasing department.

1 Warnings

- Unless already at **V4.0.1** operational code level, **DO NOT perform any code download** of the controller module : refer to the next page (FIXES point 8) for more details.
- The **V4.1.0** is the **pre-requisite CPSwitch code to use** the 622Meg 1P SMF module Long Haul (FC 6513) and 622Meg 1P SMF NEBS (FC6514) cards.
- **CPSW2 modules only: To prevent unrecoverable hardware damage, do not install a v.3.x PCMCIA card, or download v.3.x code onto the CPSW2 module (FC6502).**
- This code release supports up to 2 levels of PNNI hierarchy (level 0 and level 1).
- In case of multi-vendor ATM switches interconnection in a PNNI hierarchical network, make sure that other switches are able to exercise correctly in a full-PNNI hierarchical network, before connecting it to an 8265 IBM V4 node.
- The CPSW2 module (FC6502) includes an integrated power controller (for fan and inventory management). The module contains a **red switch** located on the bottom left of the circuit board. Before installing the CPSW2 module, check that this switch is correctly set:
 - ❖Switch OFF: Integrated Power Controller is Active.
 - ❖Switch ON: Integrated Power Controller is Inactive.
- To interconnect with 8260s, 8285s, or 8265s that do not support PNNI hierarchies, you must upgrade the code on these switches to code level v3.2.1 (for 8260/8285) and v3.3.5 (for 8265). (See *8265 Installation Guide*.)
- The CPSW2 (FC6502) does not support 8260 ATM Media Modules (no backward compatibility).
- Migration limitation from PNNI V3 code to PNNI V4 code (See section *5.3 Address Scoping for Static Reachable Addresses*).
- PNNI related commands have been modified (see *8265 Command Reference Guide*).
- At migration time from V3 to V4, all ports DEFINED as public UNI will turn to VOID..

PN 03N0367 Page 3 of 11	EC F52346A 1March1999				
----------------------------	--------------------------	--	--	--	--

This document is the property of IBM. Its use is authorized only for responding to a request for quotation or for the performance of work for IBM. All questions must be referred to the IBM purchasing department.

2 New Features

8265 Release 4.1 brings the following a new function :

- One-slot Multiprotocol Switched Services (MSS) 3.0 module (FN 5403) with an enhanced hardware version performing an average of 50% faster over MSS 2.5 module and preloaded with microcode V2R2.

PN 03N0367 Page 4 of 11	EC F52346A 1March1999				
----------------------------	--------------------------	--	--	--	--

This document is the property of IBM. Its use is authorized only for responding to a request for quotation or for the performance of work for IBM. All questions must be referred to the IBM purchasing department.

3 Fixes

1. MSS 8265 ILMI stay in ESTABLISHING state.
2. Abnormal detection of a duplicate pnni node Id
3. Node Ids (should increment the node id counter before expiration time).
4. Secure the interface_type value given to the CPT when the port is not in AUTO mode.
5. ilmi pb : get next LECS address gave wrong results
6. Default memory profile is the P2M profile on V4 code from Manuf
7. P2M should not be flagged with Frame Discard = NO
8. ILMI robustness improvement

4 Known Problems

- A module in slot 12 will be powered up by the new CPSW2 module (FC 6502) only if the chassis is a Release 4 chassis (P/N 26L0112 or 02L4093).
- The chassis level (in fact the backplane level) can be displayed at the console, by issuing the command "SHOW INVENTORY VERBOSE". Alternatively, look for a "Release 4" label on the bottom left-hand side of the front of the chassis.
- Following a power-on or CPSW module reset, the CPSW module may enter Maintenance mode with code 39 and the following message is displayed on the CPSW module LCD:
" FAT DIAG ERROR IN RB TRAFFIC MODE"
If this happens, reset the 8265 (or power off and then on again). The problem should not recur.
- When a CPSW2 module is already active in slots 11-12 and a redundant CPSW2 with integrated power control is plugged in slot 9-10, the module must be inserted quickly so as not to disturb current traffic. As the CPSW2 module powers on immediately, the insertion levers must be pressed firmly within 2 seconds of the CPSW module display being lit. Otherwise, the module may start before all connecting pins are properly seated, producing unpredictable results.
- There is no support of 8371 in this current release.
- The REVERT PNNI command may produce unpredictable results :
The "revert" command should not be used after a change in the pnni configuration followed by a "commit pnni" command. In this current release a commit pnni command must always be followed by a "save pnni" command in order to safely apply a new configuration.
- In the current release, in order to change the **pnni peer group ID** of a node keeping the same **pnni level ID**, you must follow the sequence :
 - isolate the switch from the pnni network during the complete sequence
 - change the peer group id (if changing with the node 0, the switch resets)
 - change the atm address (the switch resets)
 - reconnect the switch now reconfigured to the rest of the pnni network
 If the level Id is changed with the peer group Id, the regular procedure can be applied.

5 MIB V4

If you manage your 8265 using network management software, update your MIB to level V4 by downloading the corresponding code from Internet web page:

[http://www.networking.ibm.com/support/products.nsf/techsupport/\(8265\)?OpenDocument](http://www.networking.ibm.com/support/products.nsf/techsupport/(8265)?OpenDocument)

Following are the MIB Changes in V4 (compared to 8265 v2.3):

- The two following attributes are now R/W:
 - ♦ ocPowerOverheatPowerDownMode
 - ♦ ocPowerSlotAdminStatus
- The following attribute is new (Ptses Dump):
 - ♦ pnniDumpVertex

6 8265 Modules FPGA Levels

Module	Feature Code	Faceplate	Latest FPGA Code
CPSW	6501	CPSW	1D13
CPSW2	6502	CPSW2	2D13
155 Mbps 4P Flex module	6543	A4-MB155	1D23 (1) 2D04 (2) 3D04 (3)
155 Mbps 4P MMF Integrated module	6540	A4-MF155	1D23 (1) 2D04 (2) 3D04 (3)
622 Mbps 1P MMF module	6511	A1-MF622	2D04 (2) 3D04 (3)
622 Mbps 1P SMF Module	6512 6513 6514	A1-SF622	2D04 (2) 3D04 (3)
Carrier 2.0 module	6558	A-CMU2	2D04 (2) 3D04 (3)
Carrier 2.5 module	6559 6560 6561	A-CMU2.5S A-CMU2.5A A-WAN2.5	2D14 2D14 2D14

- (1) Applies to modules equipped with Xilinx chips 4020-3
- (2) Applies to modules equipped with Xilinx chips 4020-2
- (3) Applies to modules equipped with Xilinx chips 4036-2

PN 03N0367 Page 8 of 11	EC F52346A 1March1999				
----------------------------	--------------------------	--	--	--	--

This document is the property of IBM. Its use is authorized only for responding to a request for quotation or for the performance of work for IBM. All questions must be referred to the IBM purchasing department.

1 Documentation Update

1.1 Information from the Internet

8265 product information and code updates are available on the Internet at the following URL:

[http://www.networking.ibm.com/support/products.nsf/techsupport/\(8265\)?OpenDocument](http://www.networking.ibm.com/support/products.nsf/techsupport/(8265)?OpenDocument)

1.2 VPI_VCI Parameter of SET PORT Command

The minimum number of VCI bits, as specified with the VPI_VCI parameter of the SET PORT command, is changed to 6 for all ranges. This gives the following values:

VPI Bits	VCI Bits (25 Mbps and E1/T1)	VCI Bits (All Other Ports)
0	6-12	6-14
1-4	6-10	6-10
5-6	6-8	6-8

1.3 Address Scoping for Static Reachable Addresses

New and migrated static reachable addresses are assigned a default SCOPE value of 1-3 (PNNI level 96).

Thus, if you change the level identifier of node:0 to a higher value (for example, 88), the default static reachable addresses will not be advertised outside the node. To ensure that static reachable addresses are advertised outside such a node, use the SCOPE parameter of the SET REACHABLE ADDRESS command to change the scope of each static reachable address to, for example, '4' (PNNI level 80).

Note that there is no other way to change the scope in the current code level.

PN 03N0367 Page 9 of 11	EC F52346A 1March1999				
----------------------------	--------------------------	--	--	--	--

This document is the property of IBM. Its use is authorized only for responding to a request for quotation or for the performance of work for IBM. All questions must be referred to the IBM purchasing department.

2 Networking Rules

This section describes 8265 module performance and lists the rules to follow when building and validating your network.

2.1 ATM Peer Group Intraconnection (PNNI)

An ATM Peer Group is a group of ATM hubs or switches interconnected by Private Network-to-Network Interfaces (PNNI). The PNNI protocol supports networking functions such as routing, node failure and recovery, backup and topology management.

- **Number of Switches in the Same Peer Group:**

Depending on the network topology and complexity, the peer-group can have up to 100 nodes (assuming there are up to 200 foreign addresses and 500 links in the peer group).

- **Network Recommendations for LAN Emulation System:**

i. Limit the number of nodes to 50.

ii. Separate 8265 Network Management functions (internal LECs) from user workstations.

- **Maximum Number of Physical Links and/or PNNI VPCs per 8265: 32**

2.2 ATM Peer Group Interconnection (IISP)

Interim Inter-switch Signalling Protocol (IISP) defines the interface between two 8265s belonging to different ATM Peer Groups in the same subnetwork or in different subnetworks.

- IISP links are supported over both physical links and Virtual Path connections (VP tunneling).

- Parallel IISP links can be enabled between two clusters.

- The following limitations apply when configuring IISP ports:

- ❖ PVCs cannot be defined through IISP links. It is necessary to define a PVC on each individual Peer Group involved in the connection.

- ❖ The maximum number of reachable addresses that can be defined per 8265 is 64.

7.3 IP Over ATM (RFC 1577)

- The CPSW supports an IP client implementation to be managed over ATM (SNMP, Telnet, TFTP, Ping). The supported MTU size is 9188 bytes.

- The IP Over ATM client imbedded in the CPSW supports up to 64 concurrent IP Over ATM connections.

7.4 ATM Forum Compliant LAN Emulation Client

Each 8265 LAN Emulation Client supports up to 30 connections to other LECs.

End of document