

 ICOM

VHF AIR BAND TRANSCEIVER

IC-A4



Maximize your ground crew communications

Rugged construction

The one piece, die-cast aluminum chassis and polycarbonate front panel provide the durability needed for reliable operation under the most demanding conditions.

Simple operation

Reliable communication is essential in the hectic airport work environment. The IC-A4's large display is easy to read and shows operating status at a glance. Up/down keys allow you to change channels quickly and easily. Up to 19 memory channels can be programmed for easy recall.

PC programmable

PC programming and cloning allows you to customize each radio to your needs. Transmit can be inhibited by channel. (These features must be activated by your dealer.)

Alpha memory

The channel name function allows you to assign up to 5-character alpha names to each channel. This provides a convenient way to remember channel contents and to recognize selected channels at a glance.

Compact body

Measuring only 58(W) × 140.5(H) × 32.3(D) mm*, the IC-A4 is truly portable. Small enough to fit into a pocket.

* 2¹/₂(W) × 5⁷/₈(H) × 1¹/₂(D) in

Other features

- LCD backlighting allows you to read the display easily during nighttime operation
- Maintenance-free EEPROM stores memory channel information
- Side-tone permits hearing your own transmitted audio while using a standard aviation headset (optional headset adapter required — OPC-752)
- Standard headset cable can be used with the optional OPC-752
- Optional longer life 1050 mAh battery available, same physical size!!
- Optional (AA) alkaline battery case available — holds 8 batteries

Icom Inc.

SPECIFICATIONS

GENERAL

• Frequency range	:	118.000-136.975 MHz
Tx	:	108.000-136.975 MHz
Rx	:	6K00A3E (AM)
• Mode	:	: 19
• Number of memory channels	:	: -10°C to +50°C; +14°F to +122°F
• Usable temperature range	:	: ±10 ppm (0°C to +50°C)
• Frequency stability	:	: 9.6 V DC ±15% (negative ground)
• Power supply requirement	:	:
• Current drain (at 9.6 V DC)	:	0.7 A typical
Tx max. power	:	55 mA typical
Rx standby	:	230 mA typical
max. audio	:	BNC (50 Ω)
• Antenna connector	:	: 58(W)×140.5(H)×32.3(D) mm
• Dimensions (projections not included)	:	: 25(W)×57(H)×13(D) in
• Weight (incl. antenna and battery pack)	:	: 425 g; 15 oz (approx.)

TRANSMITTER

• Output power (typical)	:	: 3.7 W (PEP)
	:	: 1.0 W (CW)
• Modulation system	:	: Low level modulation
• Spurious emissions	:	: Less than -60 dB
• External microphone connector	:	: 3-conductor 2.5 (d) mm (1/16")/150 Ω

RECEIVER

• Receive system	:	: Double-conversion superheterodyne
• Intermediate frequencies	:	: 1st 28.95 MHz
	:	: 2nd 450 kHz
• Sensitivity (at 6 dB S/N)	:	: Less than 1.0 μV (pd)
• Squelch sensitivity	:	: Less than 1.0 μV (pd, THD)
• Selectivity	:	: More than 8 kHz/-6 dB
	:	: Less than 25 kHz/-60 dB
• Spurious response rejection ratio	:	: More than 60 dB
• Audio output power (at 9.6 V DC)	:	: More than 500 mW at 10% distortion with an 8 Ω load
• External SP connector	:	: 3-conductor 3.5 (d) mm (1/8")/8 Ω

Supplied Accessories:

- Battery pack*
- Belt clip
- Handstrap
- Wall charger*
- Antenna
- *Depending on version.

All stated specifications are subject to change without notice or obligations.

OPTIONS

BATTERY PACKS AND CASE

BP-194
R6(AA)
batteries-8*



BP-195
9.6 V, 700 mAh



BP-196
9.6 V, 1050 mAh



*Ni-Cd cells in BP-194 battery case must be purchased separately.

BC-119 DESKTOP CHARGER
+ **AD-81** DESKTOP CHARGER ADAPTER



Rapidly charge battery packs. Cannot be used to charge Ni-Cd cells installed in the BP-194. Both AC and DC can be used to power the charger. The AD-81 must be purchased separately.

BC-121 DESKTOP CHARGER
+ **AD-81** DESKTOP CHARGER ADAPTER (6 pcs.)



For rapid charging up to 6 battery packs. Cannot be used to charge Ni-Cd cells installed in the BP-194. Both AC and DC can be used to power the charger. The AD-81's must be purchased separately.

CP-12/L CIGARETTE LIGHTER CABLE WITH NOISE FILTER
OPC-254/L DC POWER CABLE



Allows you to charge the connected battery pack (13.5 to 16 V DC required). For charging ONLY—the transceiver cannot be simultaneously operated.

HM-119
SPEAKER-MICROPHONE



Durable, full-sized speaker-microphone

BC-110A/D/V WALL CHARGER
Regularly charges battery packs. The same as supplied with some versions.

OPC-474 CLONING CABLE
Used for handheld to handheld data cloning

OPC-752 HEADSET ADAPTER CABLE
Allows you to work with most aviation headsets. Provides a side tone function. This is supplied with some versions.

MB-68 BELT CLIP
The same as supplied.

Icom Inc. 6-9-16, Kamihigashi, Hirano-ku, Osaka 547, Japan Phone: 06 793 5302 Fax: 06 793 0013

Count on us!

Icom America Inc.

Corporate Headquarters
2380 118th Avenue N.E., Bellevue, WA 98004, U.S.A.
Phone: (425) 454-8155 Fax: (425) 454-1503
Telex: 152210 ICOMAMER BVUE

Customer Service
Phone: (425) 454-7619

Icom Canada

A Division of Icom America Inc.
3071 #5 Road, Unit 9, Richmond, B.C., V6X 2T4, Canada
Phone: (604) 273-7400 Fax: (604) 273-1900

Icom (Australia) Pty. Ltd.

A.C.N. 006 002 575
290-294 Albert Street, Brunswick, Victoria, 3056, Australia
Phone: 03 9387 0665 Fax: 03 9387 0022

Icom (Europe) GmbH

Communication Equipment
Himmelgaster Str. 100, D-40225 Düsseldorf, Germany
Phone: 0211 346047 Fax: 0211 333639

Icom Telecomunicaciones s.l.

"Edificio Can Castanyer" Ctra. Gracia a Manresa km. 14,750
08190 Sant Cugat Del Valles Barcelona, SPAIN
Phone: (31) 569 46 82 Fax: (31) 569 04 46

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT8 8LD, U.K.
Phone: 01227 741741 Fax: 01227 741742
Telex: 317210 BUREAU G

Icom France S.a

Zac de la Plaine, Rue Berdegonc des Moulins
BP 5804, 31505 Toulouse Cedex, France
Phone: 561 36 03 03 Fax: 561 36 03 00
Telex: 521515 ICOM FRA

Your local distributor/dealer: