



VHF/UHF DUAL BAND FM TRANSCEIVER

IC-E7

Compact body & Stylish design

- Ultra compact, lightweight body
—47×81×28 mm*, 160g**

* Projections are not included. ** Including BP-243 and antenna


- 20 hours of operating time*
with slim Lithium-Ion battery pack

* Tx:Rx:Stand-by=5:5:90 with power save on

- Wideband receiver* allows you to listen to FM, TV (audio) and others

* 0.495–999.990MHz, receiver range differs depending on version

- Minimum number of buttons
for simple operation





- VHF/UHF dual bander with 1.5W/1.0W output power

(One band at a time)

- CTCSS and DTCS tone for repeater access and quiet stand-by

- 1000 alphanumeric memory channels with flexible memory bank system

- Supplied rapid charger, BC-164, charges the battery pack in 3 hours (approx.)



Icom Inc.

Other features

- Auto memory write scan stores detected busy channels in the auto memory write bank. You can transfer them to the regular memory channels.
- Bank link scan allows you to detect busy channels from the selected banks.
- Pocket beep alerts the operator with a beep sound when the transceiver receives a signal containing a preset tone.
- Large backlit LCD with backlit buttons for night time operation
- Priority watch function checks for selected memory channel(s) every 5 seconds, while operating on VFO mode.

SPECIFICATIONS

GENERAL

• Frequency coverage (Unit: MHz) :

Version	Tx range	Rx range
EURO	144-146,430-440	0.495-999.990**
UK	144-146,430-440	0.495-999.990**
Italy	144-146,430-434,435-438	144-146,430-434,435-438
France	144-146,430-440	0.495-29.995, 50.2-51.2, 76-135.995, 144-146, 430-440**

** Guaranteed range, 144-146, 430-440MHz

- Mode : FM, AM*, WFM* *RX only
- No. of memory channels : 1252 (1000 regular, 2 call, 50 scan edges and 200 auto memory write)
- Antenna impedance : 50Ω (SMA)
- Power supply requirement : 3.7V DC (With specified battery pack)
- Usable temperature range : -10°C to +60°C
- Frequency stability : ±6ppm (-10°C to +60°C)
- Tuning step increments : 5, 6.25, 8.33, 9, 10, 12.5, 15, 20, 25, 30, 50, 100, 200kHz
- Current drain (at 3.7V DC) :
 - Transmit High : Less than 1.5A
 - Low (VHF/UHF) : 0.4A/0.5A (approx.)
 - Receive Max. audio : Less than 150mA
 - Stand-by : 80mA (approx.)
- Dimensions (W×H×D) : 47×81×28mm (Projections are not included)

- Weight (approx.) : 160g (with BP-243 and ANT)
- Ext. MIC/SP connector : 4-conductor 3.5 (d) mm /2kΩ/8Ω

TRANSMITTER

- Output power VHF : High 1.5W, Low 0.1W (approx.)
- UHF : High 1.0W, Low 0.1W (approx.)
- Max. frequency deviation : ±5.0kHz
- Spurious emissions : Less than -60dB

RECEIVER

- Intermediate frequencies : 46.35MHz, 450kHz (AM/FM)
- 14.85MHz, 450kHz (WFM)
- Sensitivity (at 12dB SINAD) : Less than 0.18μV (144/430MHz ham band only)
- Squelch sensitivity : Less than 0.18μV (at threshold; 144/430MHz ham band only)
- Selectivity AM/FM : More than 12kHz at 6dB
- Less than 30kHz at 60dB
- More than 150kHz at 10dB
- Less than 700kHz at 20dB
- WFM : More than 40dB
- Spurious rejection ratio : More than 50mW at 10% distortion with an 8Ω load
- Audio output (at 3.7V DC)

• Sensitivity (Wideband receiver general):

FM (at 12dB SINAD)	Less than
30-89.995MHz	0.45μV
90-143.995MHz	0.2μV
144-147.995MHz	0.18μV
148-179.995MHz	0.2μV
350-470MHz	0.18μV typ.
600-939.990MHz	Less than 1.4μV
940-999.990MHz	Less than 2.5μV
WFM (at 12dB SINAD)	Less than
76-107.995MHz	1.8μV
600-799.990MHz	2.5μV
AM (at 10dB S/N)	Less than
0.495-4.995MHz	2.2μV
5.00-29.995MHz	1.4μV
118-136.995MHz	1.4μV

Supplied accessories: (* Depending on version)

- Battery pack, BP-243
- AC adapter, BC-145LE/LUK*
- Battery charger, BC-164
- Antenna
- Hand strap

All stated specifications are subject to change without notice or obligation.

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.



3.7V/1800mA Li-Ion battery pack. Same as supplied.



Charges the BP-243 in 3 hours (approx). L-shaped plug AC adapter is supplied with the charger, depending on version.




For use of the BC-164 in a vehicle. (12-16V DC required.)



Allows you to put the transceiver on your belt.



Allows connection of BNC type antenna.



For transceiver to transceiver cloning.



1 plug type lapel clip microphone with earphone.



Compact and durable body. Equipped with an earphone jack. OPC-782 is required.



Light type lapel clip microphone with earphone. OPC-782 is required.



Provides clear audio in noisy environments. OPC-782 is required.



MIC/SP plug adaptor. For use with HM-131, HM-128 and SP-13.

• CS-P7 CLONING SOFTWARE + OPC-478, OPC-478U CLONING CABLES

For quick and easy programming of memory channels from a PC. (Microsoft® Windows® 98/SE/Me/2000/XP).

OPC-478: RS-232C cable, OPC-478U: USB cable

Microsoft and Windows are registered trademarks of Microsoft Corporation in the U.S.A. and other countries.

Icom Inc. 1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

2380 116th Avenue NE, Bellevue, WA 98004, U.S.A.
Phone : +1 (425) 454-8155
Fax : +1 (425) 454-1509
E-mail : sales@icomamerica.com
URL : <http://www.icomamerica.com>

Icom New Zealand

146A Harris Road, East Tamaki, Auckland, New Zealand
Phone : +64 (09) 274 4062
Fax : +64 (09) 274 4708
E-mail : inquiries@icom.co.nz
URL : <http://www.icom.co.nz>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT6 8LD, U.K.
Phone : +44 (0)1227 741741
Fax : +44 (0)1227 741742
E-mail : info@icomuk.co.uk
URL : <http://www.icomuk.co.uk>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road, Taipei, Taiwan, R.O.C.
Phone : +886 (02) 2559 1899
Fax : +886 (02) 2559 1874
E-mail : sales@asia-icom.com
URL : <http://www.asia-icom.com>

Your local distributor/dealer:

Icom Canada

Glenwood Centre #150-6165 Highway 17, Delta, B.C., V4K 5B8, Canada
Phone : +1 (604) 952-4266
Fax : +1 (604) 952-0090
E-mail : info@icomcanada.com
URL : <http://www.icomcanada.com>

Icom (Europe) GmbH

Communication Equipment Himmelgeister Str. 100, D-40225 Düsseldorf, Germany
Phone : +49 (0)211 346047
Fax : +49 (0)211 333639
E-mail : info@icom-europe.com
URL : <http://www.icom-europe.com>

Icom France S.a

Zac de la Plaine, 1, Rue Brindejonc des Moulinais BP 5804, 31505 Toulouse Cedex, France
Phone : +33 (5) 61 36 03 03
Fax : +33 (5) 61 36 03 00
E-mail : icom@icom-france.com
URL : <http://www.icom-france.com>

Beijing Icom Ltd.

10C07, Long Silver Mansion, No.88, Yong Ding Road, Haidian District, Beijing, 100039, China
Phone : +86 (010) 5889 5391/5392/5393
Fax : +86 (010) 5889 5395
E-mail : bjicom@bjicom.com
URL : <http://www.bjicom.com>

Icom (Australia) Pty. Ltd.

A.B.N. 88 006 092 575
Unit 1 / 103 Garden Road, Clayton VIC 3168 Australia
Phone : +61 (03) 9549 7500
Fax : +61 (03) 9549 7505
E-mail : sales@icom.net.au
URL : <http://www.icom.net.au>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer" 08190, Sant Cugat del Valles, Barcelona, Spain
Phone : +34 (93) 590 26 70
Fax : +34 (93) 589 04 46
E-mail : icom@icomspain.com
URL : <http://www.icomspain.com>

Icom Polska

Sopot, 3 maja 54, Poland
Phone : +48 (58) 550 7135
Fax : +48 (58) 551 0484
E-mail : icompolska@icompolska.com.pl
URL : <http://www.icompolska.com.pl>