



VHF/UHF MULTIBAND FM TRANSCEIVER

# IC-E90

*Surprisingly compact, full featured tri-bander  
with wideband receiver*

**5 Watts on 50MHz, 144MHz,  
and 430MHz**

**Wideband receiver—  
495kHz–999.990MHz!**

**555 alphanumeric memory  
channels with Icom's  
NEW DMS (Dynamic Memory Scan)  
technology!**

#### **5 Watts on 50MHz, 144MHz and 430MHz**

Enjoy a full 5 watts on all three bands from the supplied 1300mAh Lithium-Ion battery pack, BP-217. Along with the energy conserving settings, the BP-217 provides up to 5 to 6 hours\*<sup>1</sup> of operating time and greatly reduces both the size and weight needed to get full output power. Just recharge and go!

\*<sup>1</sup> Tx high: Rx: Stand-by duty ratio= 1: 1: 8

#### **Wideband receiver — 495kHz to 999.990MHz\*<sup>2</sup>**

The IC-E90 offers a wideband AM, FM, and WFM scanning receiver. Not only you can hear your favorite TV programs with the pre-programmed TV memories, but also you can listen to short-wave, AM and FM broadcast radio stations with good sound quality.

\*<sup>2</sup> Receiver range differs from depending on versions.

#### **Rugged palm sized\*<sup>3</sup>, splash resistant construction**

This compact, lightweight radio is comfortable in the smallest of hands, and offers full radio control for large fingers. The aluminum die-cast case and chassis is designed for the most rugged environments with splash resistance equivalent to JIS 4 specifications.

\*<sup>3</sup> 58(W)×87(H)×29(D) mm ; 240g (With antenna and BP-217)

#### **DTCS and CTCSS tone squelch**

A standard feature of the IC-E90 is both DTCS and CTCSS encode and decode capability. Choose from either 104 DTCS or 50 CTCSS codes for receive and transmit, individually. In addition, a pocket beep function gives you an audio alert when a matched tone signal is received — a great feature for quiet, group operations.

#### **DMS (Dynamic Memory Scan) bank scanning**

With 555 alphanumeric memory channels, including 50 band edges and 5 call channels, Icom's DMS technology gives you flexible scanning lists. With a maximum of 18 banks or 100 channels per bank, you can pick and choose the desired channel for scanning from the 500 memories.

#### **Rich in features but a simple operation**

Simple, one-handed operation is the most valuable feature of the IC-E90. The backlit ten-key pad allows you to enter frequency, memory number and set various other features. The tuning knob can be customized for channel selection, or volume control.

#### **Wait! There's more...**

- DTMF encoder with 10 memories
- Morse code synthesizer indicates the frequency in morse code
- Backlit LCD and keypad
- Auto squelch • 13 scanning modes
- High speed scanning
- PC Programmable • Antenna tip replaceable
- 5.5–11V DC operation • Split operation
- Wide/narrow transmit capability



**Icom Inc.**

SPECIFICATIONS

GENERAL

• Frequency coverage : (Unit: MHz)

Version	50MHz	144MHz	430MHz	Receive
EUR	50-52	144-146	430-440	0.495-29.995, 50-52
EUR-1	—	144-146	430-440	76-135.995
FRA	50.2-51.2	144-146	430-440	144-146, 430-440
UK	50-52	144-146	430-440	0.495-999.990
ITR	50-51	144-146	430-434, 435-438	
ESP	—	144-146	430-440	50-50.2, 144-146, 430-440

- Mode : FM, AM (Rx. only), WFM (Rx. only)
- No. of memory Ch. : 555 (500 reg., 50 scan edges, 5 call)
- Temperature range : -10°C to +60°C
- Frequency stability : ±6ppm (-10°C to +60°C)
- Power supply : 5.5 to 11V DC or specified battery pack
- Current drain (at 8.0V DC):
  - Tx High (5.0W) 2.0A typ.
  - Rx Rated audio 220mA typ.
  - standby 100mA typ.
  - Power saved 35mA typ. (duty=1:4)
- Tuning steps (kHz) : 5, 6, 25, 8.33, 9, 10, 12.5, 15, 20, 25, 30, 50, 100, 200
- Antenna impedance : 50Ω (SMA)
- Dimensions : 58(W)×87(H)×29(D) mm (projections not included)
- Weight (approx.) : 240g (with BP-217 and antenna)

TRANSMITTER

- Output power (8.0V DC): High 5W Low 0.5W
- Spurious emissions : Less than -60dB
- Max. freq. deviation : ±5.0kHz
- Ext. MIC connector : 3-conductor 2.5(d) mm/2kΩ

RECEIVER

- Receive system : Double-conversion superheterodyne
- Intermediate freq. : 1st 69.45MHz (FM/AM) 13.350MHz (WFM) 2nd 450kHz
- Sensitivity\* (typ.:except spurious points):
  - FM 1.625-4.995MHz 0.4μV
  - (at 12dB SINAD) 5-49.995MHz 0.18μV
  - 50-54MHz 0.16μV
  - 54.005-143.995MHz 0.18μV
  - 144-148MHz 0.16μV
  - 148.005-221.995MHz 0.4μV
  - 222-225MHz 0.32μV
  - 225.005-246.995MHz 0.4μV
  - 247-429.995MHz 0.32μV
  - 430-450MHz 0.16μV
  - 450.005-832.995MHz 0.32μV
  - 833-999.990MHz 1.0μV

WFM (at 12dB SINAD)	40-108MHz	1μV
	175-221.995MHz	1.8μV
	470-770MHz	3.2μV
AM (at 10dB S/N)	0.495-4.995MHz	1.3μV
	5-29.995MHz	0.56μV
	118-136MHz	0.5μV
	222-229.995MHz	0.79μV
	320-329.995MHz	1μV

- Selectivity : More than 15kHz/-9dB (except WFM) Less than 30kHz/-50dB
- Spurious and image rejection ratio:
  - 50MHz : More than 60dB (half IF: 50dB, IF: 40dB)
  - 144MHz : More than 60dB (half IF: 50dB)
  - 440MHz : More than 50dB (IF: 60dB)
- Audio output power : 200mW typ. at 10% distortion/8Ω load (at 25°C)
- AF output impedance : 8Ω

Supplied accessories (\*depending on version)

- Battery pack (BP-217)
- Wall charger\* (BC-110DR)
- Antenna
- Swivel belt clip (MB-83)

All stated specifications are subject to change without notice or obligation.

OPTIONS

BATTERY PACK AND CASE



BATTERY PACKS AND CASE		BP-216	BP-217
OUTPUT POWER		0.1W typ.	5.0W typ.
BATTERY LIFE	50MHz	—	5hours
	144/430MHz	—	6hours

Battery life is approx.time; (Tx high: Rx: Stand-by=1: 1: 8)

BC-139 DESKTOP CHARGER



Rapidly charges battery pack BP-217. Charging time (approx.): 2.5 hours.

CP-19 CIGARETTE LIGHTER CABLE WITH NOISE FILTER



Allows you to operate the transceiver with 11V DC output through a cigarette lighter socket (12V). The connected battery pack is charged simultaneously.

LC-152A CARRYING CASE



Helps protect the transceiver from scratches, etc. Fits any battery pack.

SPEAKER-MICROPHONES



- HM-46 : Slim dimensions. Equipped with an earphone jack and transmit indicator.
- HM-75A : Allows you to remotely select operating channels, etc., according to cloning.
- HM-131 : Compact and durable body. Equipped with an earphone jack and a revolving clip.

HS-94 EARHOOK-HEADSET



Flexible boom microphone and rotating earpad with a spring earhook. Use with the VS-1.

VS-1 VOX/PTT CASE



Allows you hands-free operation. Use with the HS-94.

HS-85 HEADSET



For hands-free operation. Includes VOX, PTT and "one-touch" PTT with a time-out timer.

MB-83 SWIVEL BELT CLIP



Prevents accidental dropping from your belt. Same as supplied.

SP-13 EARPHONE



Provides clear audio in noisy environments.

HM-128 EARPHONE-MICROPHONE



A light weight, compact earphone-mic. has a PTT switch that clips to your lapel.

AD-92SMA ANTENNA CONNECTOR ADAPTER



Allows you to connect a BNC-type antenna.

BC-110DR WALL CHARGER



Regularly charges battery packs. The same as supplied with some versions.

CS-T90A CLONING SOFTWARE + OPC-478 CLONING CABLE Provides quick and easy editing of memory channels, memory names and set mode contents, for local repeater frequencies, etc.

OPC-474 CLONING CABLE Used for handheld-to-handheld data cloning.

Icom Inc.

1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: 06 6793 5302 Fax: 06 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

<Corporate Headquarters>  
2380 116th Avenue N.E., Bellevue, WA 98004, U.S.A.  
Phone: (425) 454-8155 Fax: (425) 454-1509  
URL: <http://www.icomamerica.com>  
<Customer Service> Phone : (425) 454-7619

Icom Canada

Glenwood Centre #150-6165 Highway 17,  
Delta, B.C., V4K 5B8, Canada  
Phone: (604) 952-4266 Fax: (604) 952-0090  
URL: <http://www.icomcanada.com>

Icom (Australia) Pty. Ltd.

A.B.N. 88 006 092 575  
290-294 Albert Street, Brunswick, Victoria, 3056, Australia  
Phone: 03 9387 0666 Fax: 03 9387 0022  
URL: <http://www.icom.net.au>

Icom New Zealand

146A Harris Road, East Tamaki, Auckland, New Zealand  
Phone: 09 274 4062 Fax: 09 274 4708  
URL: <http://www.icom.co.nz>

Icom (Europe) GmbH

Communication Equipment  
Himmelgeister Str. 100, D-40225 Düsseldorf, Germany  
Phone: 0211 346047 Fax: 0211 333639  
URL: <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. de Gracia a Manresa Km. 14,750  
08190 Sant Cugat del Valles Barcelona, SPAIN  
Phone: (93) 590 26 70 Fax: (93) 589 04 46  
URL: <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay, Kent, CT6 8LD, U.K.  
Phone: 01227 741741 Fax: 01227 741742  
URL: <http://www.icomuk.co.uk>

Icom France S.a

Zac de la Plaine, Rue Brindejonc des Moulinais  
BP 5804, 31505 Toulouse Cedex, France  
Phone: 561 36 03 03 Fax: 561 36 03 00  
URL: <http://www.icom-france.com>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,  
Taipei, Taiwan, R.O.C.  
Phone: (02) 2559 1899 Fax: (02) 2559 1874  
URL: <http://www.asia-icom.com>

Beijing Icom Ltd.

1305, Wanshang Plaza, Shijingshan Road,  
Beijing, China  
Phone: (010) 6866 6337 Fax: (010) 6866 3553



Certificate Number Q14190  
Icom Inc. (Japan), is an ISO9001 certification acquired company.

Your local distributor/dealer: