



COMMUNICATIONS RECEIVER

IC-R10



**Tune in to the world
where ever you go...**

Wide-band, all mode receive capability

The IC-R10 has wide frequency coverage from 0.5 MHz to 1300 MHz* with all mode (incl. CW) receive capability. *Some frequency ranges may be restricted depending on country.

Real-time bandscope


The IC-R10 has a real-time bandscope function* making it easy to find busy frequencies and also easy to observe the receiving frequency band conditions. The passband width of the bandscope is selectable from the range of ± 100 kHz (20 kHz channel spacing) and ± 25 kHz (5 kHz channel spacing).

*First for a handheld receiver.

VSC function

icom's original VSC (Voice Scan Control)* function pauses scan only when modulated signals are received. And, the VSC function activates an AF mute switch when unmodulated or beat signals are received.


*Another first for a handheld receiver.



Bandscope example

Bank and memory name functions

The IC-R10 has an ample 1000 memory channels with 8-character alphanumeric names for convenience. And, channels can be grouped into banks, with each bank capable of holding a 10-character name. For protection from data loss, EEPROM's are used for memory backup.



Memory name example

New SIGNAVI function

Scan types include programmed, memory, bank, mode and more. And, introducing the new SIGNAVI scan. The SIGNAVI scan activates with programmed, auto memory write and full scans in FM mode. This scan bypasses or skips clear frequencies, within ± 100 kHz* from a paused frequency, to the next busy frequency. This helps speed up scanning.

*According to the tuning step setting:
max. acceptable tuning step is 20 kHz.

icom Inc.

More outstanding features...

- Newly-designed, tunable bandpass filters provide good image and intermodulation rejection
- 36(d) mm large internal speaker provides powerful, clear audio
- Programmable from a PC as well as receiver to receiver cloning capability (optional CS-R10+OPC-478 or OPC-479 is required)
- Multi-function, dot-matrix LCD displays a variety of information
- User-programmable TS (between 0.1 and 999.9 kHz in 0.1 kHz steps)
- Auto mode and TS for simplified operation
- Memory edit function for easy editing or revision of memory contents
- Memory copy function
- Easy mode provides simplified scanning operation
- CI-V compatibility (optional CT-17 required)
- Built-in 20 dB attenuator
- AFC (Auto Frequency Control) function
- Noise blanker and ANL (Auto Noise Limiter) functions

SPECIFICATIONS**GENERAL**

- Frequency range : (Unit: MHz)

Version	Frequency Range
U.S.A.	0.5000-823.9999
	849.0001-868.9999
	894.0001-1300.0000
Europe	0.5000-1300.0000
France	0.5000-87.5000
	108.0000-1300.0000

- Mode : FM, WFM, AM, USB, LSB, CW
- Tuning steps : 0.1, 0.5, 1, 5, 6.25, 8, 9, 10, 12.5, 15, 20, 25, 30, 50, 100 kHz or user-programmable (0.1-999.9 kHz/0.1 kHz steps)
- Power supply requirement : 4.8 V DC (+ AA (R6) Ni-Cd cells), or 4.8-16 V DC acceptable (negative ground)
- Current drain (at 13.5 V DC):
Rated audio 180 mA typ.
Standby 110 mA typ.
Power saved 38 mA typ.
- Usable temp. range : -10°C to +50°C (+14°F to +122°F)
- Antenna connector : BNC (50 Ω)

- CI-V connector : 3-conductor 3.5(d) mm (1/8")
- Dimensions : 58.5(W) x 130(H) x 31.3(D) mm
2.3(W) x 5.1(H) x 1.2(D) in
- Weight : 310 g; 10.9 oz.

RECEIVER

- Receive system : Triple superheterodyne
- Intermediate freq. :
1st : 266.7 MHz (340.0000-999.9999)
429.1 MHz (except above freq.)
2nd : 10.7 MHz
3rd : 455 kHz
- Sensitivity (typ.) : (except spurious points)

Freq. (MHz)	FM	WFM	AM	SSB/CW
0.5- 4.9999	0.5 μV	—	1.6 μV	0.4 μV
5- 74.9999	0.32 μV	—	1.0 μV	0.25 μV
75- 199.9999	—	1.0 μV	—	—
200- 339.9999	0.45 μV	2.2 μV	1.6 μV	0.4 μV
340- 699.9999	0.35 μV	1.3 μV	1.4 μV	0.32 μV
700- 799.9999	0.79 μV	2.0 μV	2.0 μV	0.63 μV
800- 899.9999	0.5 μV	1.6 μV	1.6 μV	0.4 μV
900-1300.0000	—	—	—	—

*FM and WFM are measured at 12 dB SINAD; AM, SSB and CW are measured at 10 dB S/N.

- Squelch sensitivity : (at threshold)

Freq. (MHz)	FM	WFM	AM
0.5- 4.9999	0.5 μV	—	1.6 μV
5- 74.9999	—	—	—
75- 199.9999	0.32 μV	1.0 μV	1.0 μV
200- 339.9999	0.45 μV	2.2 μV	1.6 μV
340- 699.9999	0.35 μV	1.3 μV	1.4 μV
700- 799.9999	0.79 μV	2.0 μV	2.0 μV
800- 899.9999	0.5 μV	1.6 μV	1.6 μV
900-1300.0000	—	—	—

- Selectivity :
SSB, CW : More than 4 kHz/6 dB
AM, FM : More than 15 kHz/6 dB
WFM : More than 150 kHz/6 dB
- Audio output power : More than 120 mW at 10% distortion with an 8 Ω (at 13.5 V DC) load
- External speaker : 3-conductor 3.5(d) mm (1/8") 8 Ω connector

All stated specifications are subject to change without notice or obligation.

OPTIONS

- **CS-R10 CLONING SOFTWARE + OPC-478 CLONING CABLE**
Allows you to transfer data from memories, etc., quickly and easily between IC-R10's as well as edit and store data via an IBM compatible PC.
- **LC-140 CARRYING CASE**
For protecting the receiver.
- **CT-17 CI-V LEVEL CONVERTOR**
For receiver remote control using an IBM-compatible personal computer.
- **HP-4 HEADPHONE/SP-13 EARPHONE**
Provide increased readability of signals in noisy environments and listening privacy.
- **CP-12L CIGARETTE LIGHTER CABLE WITH NOISE FILTER**
Allows you to operate the receiver through a 12 V cigarette lighter socket.
- **OPC-254L POWER CABLE**
Allows you to operate the receiver with 4.5 to 16 V external DC power.
- **OPC-474 CLONING CABLE**
Allows you to transfer data between receivers.



LC-140



CT-17



HP-4



CP-12L



OPC-254L

Icom Inc. 6-9-16, Kamihigashi, Hirano-ku, Osaka 547, Japan Phone: 06 793 5302 Fax: 06 793 0013

Count on us!

Icom America Inc.

<Corporate Headquarters>
2390 116th Avenue N.E., Bellevue, WA 98004, U.S.A.
Phone: (206) 454-8155 Fax: (206) 454-1529
Telex: 152210 ICOM AMER BVUE

<Customer Service>
Phone: (206) 454-7619

Icom Canada

A Division of Icom America Inc.
3071 #5 Road, Unit 9, Richmond, B.C., V6X 2T4, Canada
Phone: (604) 273-7400 Fax: (604) 273-1900

Icom (Europe) GmbH

Communication Equipment
Himmelgasser Str. 100, D-40225 Düsseldorf, Germany
Phone: 0211 346047 Fax: 0211 333639

Icom (Australia) Pty. Ltd.

A.C.N. 006 082 575
290-294 Albert Street, Brunswick, Victoria, 3056, Australia
Phone: 03 9387 0666 Fax: 03 9387 0022

Icom (UK) Ltd.

Unit 9, Sea St, Heme Bay, Kent, CT6 6LD, U.K.
Phone: 01227 741741 Fax: 01227 741742
Telex: 317210 BUREAU G

Icom France Sa

Zac de la Poine, Rue Brindejonc des Moulineaux
BP 5804, 31505 Toulouse Cedex, France
Phone: 561 36 03 03 Fax: 561 36 03 00
Telex: 521515 ICOM FRA

Your local distributor/dealer: