

# PRINTED WIRING BOARD PARTS LIST (AV-21LS/C)

## MAIN PW BOARD ASS'Y (SCH-1062A-H2)

△ Symbol No.	Part No.	Part Name	Description	Local	△ Symbol No.	Part No.	Part Name	Description	Local
<b>RESISTOR</b>					<b>RESISTOR</b>				
R1001-02	NRSA63J-221X	MG R	220Ω 1/16W	J	R1531	NRSA63J-222X	MG R	2.2kΩ 1/16W	J
R1003	NRSA63J-392X	MG R	3.9kΩ 1/16W	J	△ R1532	QRZ9017-4R7	F R	4.7Ω 1/4W	J
R1004	NRSA63J-221X	MG R	220Ω 1/16W	J	△ R1540	QRZ9011-4R7	F R	4.7Ω 1/2W	J
R1006	NRSA63J-273X	MG R	27kΩ 1/16W	J	R1541-42	QRE121J-154Y	C R	150kΩ 1/2W	J
R1101	NRSA63J-100X	MG R	10Ω 1/16W	J	R1543	QRE121J-471Y	C R	470Ω 1/2W	J
R1102	NRSA63J-682X	MG R	6.8kΩ 1/16W	J	R1545	QRE121J-220Y	C R	22Ω 1/2W	J
R1103	NRSA63J-272X	MG R	2.7kΩ 1/16W	J	R1546	QRE121J-822Y	C R	8.2kΩ 1/2W	J
R1104	NRSA63J-181X	MG R	180Ω 1/16W	J	R1591	QRE121J-222Y	C R	2.2kΩ 1/2W	J
R1105	NRSA63J-220X	MG R	22Ω 1/16W	J	R1592	QRZ0221-2R2	UNF R	2.2Ω	
R1106	NRSA63J-101X	MG R	100Ω 1/16W	J	R1593	NRSA63J-102X	MG R	1kΩ 1/16W	J
R1107	NRSA63J-472X	MG R	4.7kΩ 1/16W	J	R1594	QRE121J-183Y	C R	18kΩ 1/2W	J
R1108-10	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	R1595	NRSA63J-222X	MG R	2.2kΩ 1/16W	J
R1111	NRSA63J-102X	MG R	1kΩ 1/16W	J	R1602	NRSA63J-271X	MG R	270Ω 1/16W	J
R1112	NRSA63J-103X	MG R	10kΩ 1/16W	J	R1603-04	NRSA63J-101X	MG R	100Ω 1/16W	J
R1113	NRSA63J-271X	MG R	270Ω 1/16W	J	R1605	QRE141J-0R0Y	C R	0.0Ω 1/4W	J
R1114	NRSA63J-821X	MG R	820Ω 1/16W	J	R1621-22	NRSA63J-101X	MG R	100Ω 1/16W	J
R1115	NRSA63J-181X	MG R	180Ω 1/16W	J	R1650	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1117	NRSA63J-102X	MG R	1kΩ 1/16W	J	R1651	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
R1119	NRSA63J-102X	MG R	1kΩ 1/16W	J	R1652-53	NRSA63J-222X	MG R	2.2kΩ 1/16W	J
R1120	NRSA63J-471X	MG R	470Ω 1/16W	J	R1654	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1150	NRSA63J-331X	MG R	330Ω 1/16W	J	R1655	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
R1151	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	R1658-59	QRE121J-2R2Y	C R	2.2Ω 1/2W	J
R1152	NRSA63J-121X	MG R	120Ω 1/16W	J	R1660	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1153	NRSA63J-122X	MG R	1.2kΩ 1/16W	J	R1661	NRSA63J-683X	MG R	68kΩ 1/16W	J
R1154	NRSA63J-181X	MG R	180Ω 1/16W	J	R1662	NRSA63J-333X	MG R	33kΩ 1/16W	J
R1301-02	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	R1663	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1303	NRSA63J-562X	MG R	5.6kΩ 1/16W	J	R1664	NRSA63J-222X	MG R	2.2kΩ 1/16W	J
R1304-05	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	R1665-66	QRE141J-561Y	C R	560Ω 1/4W	J
R1306	NRSA63J-562X	MG R	5.6kΩ 1/16W	J	R1667	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1350-51	NRSA63J-151X	MG R	150Ω 1/16W	J	R1668	NRSA63J-683X	MG R	68kΩ 1/16W	J
R1353	NRSA63J-151X	MG R	150Ω 1/16W	J	R1669	NRSA63J-563X	MG R	56kΩ 1/16W	J
R1354	QRE121J-222Y	C R	2.2kΩ 1/2W	J	R1670	NRSA63J-153X	MG R	15kΩ 1/16W	J
R1363	QRZ0107-152Z	C R	1.5kΩ 1/2W	K	R1671	NRSA63J-272X	MG R	2.7kΩ 1/16W	J
R1364	QRE121J-222Y	C R	2.2kΩ 1/2W	J	R1672	NRSA63J-563X	MG R	56kΩ 1/16W	J
R1365	QRZ0107-152Z	C R	1.5kΩ 1/2W	K	R1673-74	NRSA63J-683X	MG R	68kΩ 1/16W	J
R1366	QRZ0107-474Z	C R	470kΩ 1/2W	K	R1675	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1368	QRZ0107-152Z	C R	1.5kΩ 1/2W	K	R1676-77	NRSA63J-472X	MG R	4.7kΩ 1/16W	J
R1369	QRE121J-222Y	C R	2.2kΩ 1/2W	J	R1678	NRSA63J-153X	MG R	15kΩ 1/16W	J
R1373	QRE121J-394Y	C R	390kΩ 1/2W	J	R1679	NRSA63J-272X	MG R	2.7kΩ 1/16W	J
R1374	QRE121J-124Y	C R	120kΩ 1/2W	J	R1680	NRSA63J-683X	MG R	68kΩ 1/16W	J
R1380-83	NRSA63J-101X	MG R	100Ω 1/16W	J	R1688	NRSA63J-273X	MG R	27kΩ 1/16W	J
R1384	NRSA63J-223X	MG R	22kΩ 1/16W	J	R1690	NRSA63J-104X	MG R	100kΩ 1/16W	J
R1401	NRSA63J-224X	MG R	220kΩ 1/16W	J	R1691	NRSA63J-682X	MG R	6.8kΩ 1/16W	J
R1403	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J	R1692	NRSA63J-104X	MG R	100kΩ 1/16W	J
R1405	NRSA63J-682X	MG R	6.8kΩ 1/16W	J	R1693	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1406	NRSA63J-123X	MG R	12kΩ 1/16W	J	R1696	NRSA63J-222X	MG R	2.2kΩ 1/16W	J
R1408	NRSA63J-682X	MG R	6.8kΩ 1/16W	J	R1698-99	NRSA63J-104X	MG R	100kΩ 1/16W	J
R1410	NRSA63J-123X	MG R	12kΩ 1/16W	J	R1701	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1411	QRG01GJ-221	OM R	220Ω 1W	J	R1702-03	NRSA63J-101X	MG R	100Ω 1/16W	J
R1412	QRE121J-1R0Y	C R	1.0Ω 1/2W	J	R1704-06	NRSA63J-102X	MG R	1kΩ 1/16W	J
R1413	QRX01GJ-5R6	MF R	5.6Ω 1W	J	R1707-10	NRSA63J-472X	MG R	4.7kΩ 1/16W	J
R1414	QRE121J-6R8Y	C R	6.8Ω 1/2W	J	R1711-14	NRSA63J-101X	MG R	100Ω 1/16W	J
R1425	NRSA63J-683X	MG R	68kΩ 1/16W	J	R1715-17	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1480	QRE121J-681Y	C R	680Ω 1/2W	J	R1718-19	NRSA63J-221X	MG R	220Ω 1/16W	J
R1481	NRSA63J-223X	MG R	22kΩ 1/16W	J	R1720	NRSA63J-102X	MG R	1kΩ 1/16W	J
R1482	NRSA63J-562X	MG R	5.6kΩ 1/16W	J	R1721-24	NRSA63J-221X	MG R	220Ω 1/16W	J
R1483	NRSA63J-823X	MG R	82kΩ 1/16W	J	R1725	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1484-85	NRSA63J-562X	MG R	5.6kΩ 1/16W	J	R1726	NRSA63J-472X	MG R	4.7kΩ 1/16W	J
R1486	NRSA63J-272X	MG R	2.7kΩ 1/16W	J	R1727	NRSA63J-104X	MG R	100kΩ 1/16W	J
R1487	NRSA63J-333X	MG R	33kΩ 1/16W	J	R1728	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1489	NRSA63J-122X	MG R	1.2kΩ 1/16W	J	R1730	NRSA63J-223X	MG R	22kΩ 1/16W	J
R1490	NRSA63J-102X	MG R	1kΩ 1/16W	J	R1731	NRSA63J-101X	MG R	100Ω 1/16W	J
R1491	NRSA63J-562X	MG R	5.6kΩ 1/16W	J	R1732	NRSA63J-393X	MG R	39kΩ 1/16W	J
R1492	NRSA63J-822X	MG R	8.2kΩ 1/16W	J	R1733	NRSA63J-273X	MG R	27kΩ 1/16W	J
R1493	QRE121J-223Y	C R	22kΩ 1/2W	J	R1734	NRSA63J-391X	MG R	390Ω 1/16W	J
R1494	QRL03EJ-330X	OM R	33Ω 3W	J	R1735	NRSA63J-104X	MG R	100kΩ 1/16W	J
R1521	NRSA63J-101X	MG R	100Ω 1/16W	J	R1736	NRSA63J-333X	MG R	33kΩ 1/16W	J
R1522	NRSA63J-102X	MG R	1kΩ 1/16W	J	R1737	NRSA63J-272X	MG R	2.7kΩ 1/16W	J
R1524	QRL02EJ-270X	OM R	27Ω 2W	J	R1738	NRSA63J-103X	MG R	10kΩ 1/16W	J
R1526	QRG01GJ-271	OM R	270Ω 1W	J	R1739-41	NRSA63J-101X	MG R	100Ω 1/16W	J
R1527	QRL03EJ-103X	OM R	10kΩ 3W	J	R1742	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
R1528-29	QRX029J-1R2	MF R	1.2Ω 2W	J	R1743	QRE141J-102Y	C R	1kΩ 1/4W	J

△	Symbol No.	Part No.	Part Name	Description	Local	△	Symbol No.	Part No.	Part Name	Description	Local
<b>RESISTOR</b>						<b>RESISTOR</b>					
	R1744	NRSA63J-561X	MG R	560Ω 1/16W	J	R1953	NRSA63J-101X	MG R	100Ω 1/16W	J	
	R1745	NRSA63J-105X	MG R	1MΩ 1/16W	J	R1954	QRE121J-560Y	C R	56Ω 1/2W	J	
	R1746	NRSA63J-333X	MG R	33kΩ 1/16W	J	R1955	QRG01GJ-330	OM R	33Ω 1W	J	
	R1747	NRSA63J-103X	MG R	10kΩ 1/16W	J	R1956	QRE121J-100Y	C R	10Ω 1/2W	J	
	R1748-49	NRSA02J-475X	MG R	4.7MΩ 1/10W	J	R1957	QRE121J-6R8Y	C R	6.8Ω 1/2W	J	
	R1750-51	QRE141J-0R0Y	C R	0.0Ω 1/4W	J	R1960	NRSA63J-391X	MG R	390Ω 1/16W	J	
	R1755-56	NRSA63J-101X	MG R	100Ω 1/16W	J	R1961	QRL02EJ-223X	OM R	22kΩ 2W	J	
	R1757-58	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	R1962	NRSA63J-561X	MG R	560Ω 1/16W	J	
	R1760	NRSA63J-682X	MG R	6.8kΩ 1/16W	J	R1963	QRE121J-103Y	C R	10kΩ 1/2W	J	
	R1770	QRE121J-271Y	C R	270Ω 1/2W	J	R1964	NRSA63J-473X	MG R	47kΩ 1/16W	J	
	R1771	NRSA63J-102X	MG R	1kΩ 1/16W	J	R1965	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J	
	R1772	QRE121J-271Y	C R	270Ω 1/2W	J	R1966	NRSA63J-682X	MG R	6.8kΩ 1/16W	J	
	R1773	NRSA63J-102X	MG R	1kΩ 1/16W	J	R1967	NRSA63J-473X	MG R	47kΩ 1/16W	J	
	R1775	NRSA63J-332X	MG R	3.3kΩ 1/16W	J	R1970	NRSA63J-153X	MG R	15kΩ 1/16W	J	
	R1776	NRSA63J-392X	MG R	3.9kΩ 1/16W	J	R1971	NRSA63J-183X	MG R	18kΩ 1/16W	J	
	R1777	NRSA63J-682X	MG R	6.8kΩ 1/16W	J	△	R1991	QRZ0057-825	C R	8.2MΩ 1W	J
	R1779	NRSA63J-272X	MG R	2.7kΩ 1/16W	J	<b>CAPACITOR</b>					
	R1780	NRSA63J-471X	MG R	470Ω 1/16W	J	C1001	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	R1781	NRSA63J-122X	MG R	1.2kΩ 1/16W	J	C1002	QETN1HM-106Z	E CAP.	10μF 50V	M	
	R1782	NRSA63J-181X	MG R	180Ω 1/16W	J	C1003	QFV71HJ-104Z	MF CAP.	0.1μF 50V	J	
	R1783	NRSA63J-221X	MG R	220Ω 1/16W	J	C1004	QETN1CM-477Z	E CAP.	470μF 16V	M	
	R1784	NRSA63J-331X	MG R	330Ω 1/16W	J	C1005	NCB31HK-222X	C CAP.	2200pF 50V	K	
	R1785	NRSA63J-471X	MG R	470Ω 1/16W	J	C1006	QETN1CM-336Z	E CAP.	33μF 16V	M	
	R1803	NRSA63J-333X	MG R	33kΩ 1/16W	J	C1007	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	R1805	NRSA63J-750X	MG R	75Ω 1/16W	J	C1101-05	NCB31HK-472X	C CAP.	4700pF 50V	K	
	R1808	NRSA63J-823X	MG R	82kΩ 1/16W	J	C1106-07	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	R1809	NRSA63J-391X	MG R	390Ω 1/16W	J	C1108	NCB31HK-472X	C CAP.	4700pF 50V	K	
	R1810	NRSA63J-823X	MG R	82kΩ 1/16W	J	C1109	QETN1HM-106Z	E CAP.	10μF 50V	M	
	R1811	NRSA63J-391X	MG R	390Ω 1/16W	J	C1150-51	NCB31HK-472X	C CAP.	4700pF 50V	K	
	R1812	NRSA63J-104X	MG R	100kΩ 1/16W	J	C1308	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	R1813	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	C1352	QFK62EK-104Z	MM CAP.	0.1μF 250V	K	
	R1815	NRSA63J-101X	MG R	100Ω 1/16W	J	C1353	QETN2EM-475Z	E CAP.	4.7μF 250V	M	
	R1818	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	C1354	QCZ0131-222	C CAP.	2200pF 2000V	K	
	R1820	NRSA63J-101X	MG R	100Ω 1/16W	J	C1355	QCZ0131-472	C CAP.	4700pF 2000V	K	
	R1821	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	C1357	NDC31HJ-101X	C CAP.	100pF 50V	J	
	R1823	NRSA63J-101X	MG R	100Ω 1/16W	J	C1358	QETN1CM-477Z	E CAP.	470μF 16V	M	
	R1824	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	C1401	QETN1HM-105Z	E CAP.	1μF 50V	M	
	R1826	NRSA63J-101X	MG R	100Ω 1/16W	J	C1402	QCB31HK-682Z	C CAP.	6800pF 50V	K	
	R1829	NRSA63J-750X	MG R	75Ω 1/16W	J	C1403	QEHR1VM-227Z	E CAP.	220μF 35V	M	
	R1830-31	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	C1406	QFLC2AJ-683Z	M CAP.	0.068μF 100V	J	
	R1832	NRSA63J-122X	MG R	1.2kΩ 1/16W	J	C1408	QFV71HJ-184Z	MF CAP.	0.18μF 50V	J	
	R1833	NRSA63J-102X	MG R	1kΩ 1/16W	J	C1411-12	NCF21HZ-334X	C CAP.	0.33μF 50V	Z	
	R1834-35	NRSA63J-562X	MG R	5.6kΩ 1/16W	J	C1413	QFLC2AJ-563Z	M CAP.	0.056μF 100V	J	
	R1836	NRSA63J-750X	MG R	75Ω 1/16W	J	C1422	QETN1VM-108Z	E CAP.	1000μF 35V	M	
	R1837	NRSA63J-101X	MG R	100Ω 1/16W	J	C1480	QETN1HM-106Z	E CAP.	10μF 50V	M	
	R1838	QRK126J-121X	C R	120Ω 1/2W	J	C1483	QEZ0195-475Z	E CAP.	4.7μF 50V	M	
	R1839-40	QRE121J-221Y	C R	220Ω 1/2W	J	C1485	QETN1HM-226Z	E CAP.	22μF 50V	M	
	R1841-42	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J	C1521	QETN1VM-476Z	E CAP.	47μF 35V	M	
	R1843	NRSA63J-821X	MG R	820Ω 1/16W	J	C1522	QFLC1HJ-332Z	M CAP.	3300pF 50V	J	
	R1844	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	C1523	QFLC1HJ-223Z	M CAP.	0.022μF 50V	J	
	R1845	NRSA63J-102X	MG R	1kΩ 1/16W	J	C1524	QFZ0196-602	MPP CAP.	6000pF 1.5KVH ±3%		
	R1846	NRSA63J-222X	MG R	2.2kΩ 1/16W	J	C1525	QFZ0196-472	MPP CAP.	4700pF 1.5KVH ±3%		
	R1847	NRSA63J-103X	MG R	10kΩ 1/16W	J	C1526	QFP32GJ-183	PP CAP.	0.018μF 400V	J	
	R1848	NRSA63J-471X	MG R	470Ω 1/16W	J	C1527-28	QFZ0199-154	MPP CAP.	0.15μF 250V	J	
	R1849	NRSA63J-221X	MG R	220Ω 1/16W	J	C1529	QEHR2EM-475Z	E CAP.	4.7μF 250V	M	
	R1880	NRSA63J-202X	MG R	2kΩ 1/16W	J	C1530	QCB32HK-561Z	C CAP.	560pF 500V	K	
	R1881	NRSA63J-103X	MG R	10kΩ 1/16W	J	C1531	QEHR1EM-108Z	E CAP.	1000μF 25V	M	
	R1882	NRSA63J-471X	MG R	470Ω 1/16W	J	C1533	QEHR1EM-108Z	E CAP.	1000μF 25V	M	
	R1883	NRSA63J-181X	MG R	180Ω 1/16W	J	C1535	QCB32HK-101Z	C CAP.	100pF 500V	K	
	R1884-85	QRE141J-750Y	C R	75Ω 1/4W	J	C1536	QFLC1HJ-103Z	M CAP.	0.01μF 50V	J	
	R1898	QRE141J-750Y	C R	75Ω 1/4W	J	C1540	QFV71HJ-104Z	MF CAP.	0.1μF 50V	J	
	R1902	QRF154K-2R2	UNF R	2.2Ω 15W	K	C1541	QETN2EM-106Z	E CAP.	10μF 250V	M	
	R1904	QRE121J-681Y	C R	680Ω 1/2W	J	C1550	NCB31CK-104X	C CAP.	0.1μF 16V	K	
	R1905	QRM034J-R22	MP R	0.22Ω 3W	J	C1591	QETN1AM-107Z	E CAP.	100μF 10V	M	
	R1907	NRSA63J-563X	MG R	56kΩ 1/16W	J	C1592	QEZ0203-107	E CAP.	100μF 160V	M	
	R1908	QRL039J-333	OM R	33kΩ 3W	J	C1593	QETN1EM-476Z	E CAP.	47μF 25V	M	
	R1909	QRE121J-474Y	C R	470kΩ 1/2W	J	C1602	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	R1910	QRE121J-392Y	C R	3.9kΩ 1/2W	J	C1603	QETN1CM-107Z	E CAP.	100μF 16V	M	
	R1911	QRE121J-332Y	C R	3.3kΩ 1/2W	J	C1604	NCB31CK-104X	C CAP.	0.1μF 16V	K	
	R1912	NRSA63J-182X	MG R	1.8kΩ 1/16W	J	C1606-07	NDC31HJ-2R0X	C CAP.	2.0pF 50V	J	
△	R1915	QRZ0111-474	C R	470kΩ 1/2W	K	C1608-09	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	R1952	NRSA63J-332X	MG R	3.3kΩ 1/16W	J	C1610	QETN1HM-106Z	E CAP.	10μF 50V	M	
						C1611	NCB31CK-104X	C CAP.	0.1μF 16V	K	

△ Symbol No.	Part No.	Part Name	Description	Local
<b>CAPACITOR</b>				
C1612	QETN1HM-106Z	E CAP.	10μF 50V M	
C1613	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1615	QETN1HM-106Z	E CAP.	10μF 50V M	
C1616	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1617	QETN1HM-106Z	E CAP.	10μF 50V M	
C1619	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1620	QETN1HM-106Z	E CAP.	10μF 50V M	
C1621-22	NCB31HK-102X	C CAP.	1000pF 50V K	
C1623-24	NCF31AZ-105X	C CAP.	1μF 10V Z	
C1650	QEHR1HM-106Z	E CAP.	10μF 50V M	
C1651	QETN1HM-107Z	E CAP.	100μF 50V M	
C1652	QETN1HM-106Z	E CAP.	10μF 50V M	
C1655-56	QETM1VM-108	E CAP.	1000μF 35V M	
C1659-61	NCF21HZ-224X	C CAP.	0.22μF 50V Z	
C1662	QETN1HM-106Z	E CAP.	10μF 50V M	
C1663	NCF21HZ-224X	C CAP.	0.22μF 50V Z	
C1665	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1666-67	QFLC1HJ-153Z	M CAP.	0.015μF 50V J	
C1668-69	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1670	NCB31HK-223X	C CAP.	0.022μF 50V K	
C1671	QETN1CM-476Z	E CAP.	47μF 16V M	
C1672	NCB31HK-473X	C CAP.	0.047μF 50V K	
C1673	QETN1CM-336Z	E CAP.	33μF 16V M	
C1674	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1675	NCB31HK-473X	C CAP.	0.047μF 50V K	
C1676	NCB31HK-223X	C CAP.	0.022μF 50V K	
C1681-82	QETN1CM-227Z	E CAP.	220μF 16V M	
C1683	QETM1CM-336Z	E CAP.	33μF 16V M	
C1685-86	NCF31AZ-105X	C CAP.	1μF 10V Z	
C1702	QETN1HM-106Z	E CAP.	10μF 50V M	
C1703-04	NDC31HJ-220X	C CAP.	22pF 50V J	
C1706	NCB21EK-224X	C CAP.	0.22μF 25V K	
C1707	QETN1CM-107Z	E CAP.	100μF 16V M	
C1709	QETN1CM-107Z	E CAP.	100μF 16V M	
C1710	NCB21EK-224X	C CAP.	0.22μF 25V K	
C1711	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1713	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1714	QETN1CM-476Z	E CAP.	47μF 16V M	
C1720	QETN1CM-476Z	E CAP.	47μF 16V M	
C1725	NCB31HK-681X	C CAP.	680pF 50V K	
C1726	QETN1HM-106Z	E CAP.	10μF 50V M	
C1730-31	NCB21EK-224X	C CAP.	0.22μF 25V K	
C1732	QETN1CM-107Z	E CAP.	100μF 16V M	
C1733	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1734-35	NCB31HK-222X	C CAP.	2200pF 50V K	
C1736-37	QETN1HM-105Z	E CAP.	1μF 50V M	
C1738	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1739	NFV41CJ-104X	MPP CAP.	0.1μF 16V J	
C1740	QETN1HM-225Z	E CAP.	2.2μF 50V M	
C1741-42	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1743	QETN1CM-107Z	E CAP.	100μF 16V M	
C1744	NCB21HK-102X	C CAP.	1000pF 50V K	
C1745-47	NCB31EK-473X	C CAP.	0.047μF 25V K	
C1749	QETN1HM-106Z	E CAP.	10μF 50V M	
C1751-53	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1760	NCB21EK-104X	C CAP.	0.1μF 25V K	
C1761	QETN1CM-107Z	E CAP.	100μF 16V M	
C1770	QETN1HM-106Z	E CAP.	10μF 50V M	
C1801-04	QETN1HM-106Z	E CAP.	10μF 50V M	
C1805	QFLC1HJ-104Z	M CAP.	0.1μF 50V J	
C1807-08	NCF31AZ-105X	C CAP.	1μF 10V Z	
C1810	NCF31AZ-105X	C CAP.	1μF 10V Z	
C1811	QFLC1HJ-104Z	M CAP.	0.1μF 50V J	
C1812	NCF31AZ-105X	C CAP.	1μF 10V Z	
C1813	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1814	QFLC1HJ-104Z	M CAP.	0.1μF 50V J	
C1815	NCF31AZ-105X	C CAP.	1μF 10V Z	
C1817	NCF31AZ-105X	C CAP.	1μF 10V Z	
C1819	QFLC1HJ-104Z	M CAP.	0.1μF 50V J	
C1820-21	NCF31AZ-105X	C CAP.	1μF 10V Z	
C1822	QETN1CM-477Z	E CAP.	470μF 16V M	
C1823-24	QETN1CM-107Z	E CAP.	100μF 16V M	

△ Symbol No.	Part No.	Part Name	Description	Local
<b>CAPACITOR</b>				
C1825	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1826	QFLC1HJ-104Z	M CAP.	0.1μF 50V J	
C1827	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1829-31	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1833	QETN1HM-226Z	E CAP.	22μF 50V M	
C1834	NDC31HJ-181X	C CAP.	180pF 50V J	
△ C1901	QFZ9073-104	MF CAP.	0.1μF	
△ C1902	QFZ9073-473	MF CAP.	0.047μF	
C1903-05	QCZ9015-102Z	C CAP.	1000pF 250V Z	
△ C1906	QFZ9073-224	MF CAP.	0.22μF	
C1907	QEZO199-227	E CAP.	220μF 400V M	
C1908	QCZ0364-222	C CAP.	2200pF	
C1910	NDC21HJ-471X	C CAP.	470pF 50V J	
C1911	QETN1EM-227Z	E CAP.	220μF 25V M	
C1914	QETN1EM-227Z	E CAP.	220μF 25V M	
C1915	QFLC1HJ-222Z	M CAP.	2200pF 50V J	
C1952	QCB32HK-471Z	C CAP.	470pF 500V K	
C1953	QEHR1VM-108Z	E CAP.	1000μF 35V M	
C1954	NCB31HK-102X	C CAP.	1000pF 50V K	
C1957	QCB32HK-471Z	C CAP.	470pF 500V K	
C1958	QETN1CM-108Z	E CAP.	1000μF 16V M	
C1959	QCZ0364-561	C CAP.	560pF	
C1960	QEZO203-107	E CAP.	100μF 160V M	
C1962	QETN1HM-106Z	E CAP.	10μF 50V M	
C1963	QETN1CM-476Z	E CAP.	47μF 16V M	
C1964	QEHR1VM-476Z	E CAP.	47μF 35V M	
C1968	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1972	QETN1HM-476Z	E CAP.	47μF 50V M	
C1973	QETN1AM-107Z	E CAP.	100μF 10V M	
C1974	NCB31CK-104X	C CAP.	0.1μF 16V K	
C1975	QETN1CM-227Z	E CAP.	220μF 16V M	
C1976	QETN1AM-107Z	E CAP.	100μF 10V M	
C1977	QETN1EM-476Z	E CAP.	47μF 25V M	
C1978	NCB21HK-104X	C CAP.	0.1μF 50V K	
C1980	QETN1CM-107Z	E CAP.	100μF 16V M	
△ C1991-93	QCZ9079-102	C CAP.	1000pF 250V M	
<b>TRANSFORMER</b>				
T1521	CE40203-00CJ1	DRIVE TRANSF.		
△ T1551	QQH0104-001	H.V.TRANSF.		
△ T1901	QQS0117-001	SWTICH.TRANSF.		
<b>COIL</b>				
L1001-02	QQL244K-8R2Z	COIL	8.2μH	K
L1101-02	QQL244J-5R6Z	COIL	5.6μH	J
L1103	QQL244K-100Z	COIL	10μH	K
L1104	QQL244K-180Z	COIL	18μH	K
L1351	QQL03BJ-5R6Z	COIL	5.6μH	J
L1480	QQLZ016-821	CHOKE COIL	820μH	
L1523	QQR1005-002	LIINIARITY COIL		
L1524	QQLZ034-430	CHOKE COIL	43μH	
L1601	QQL244K-4R7Z	COIL	4.7μH	K
L1602	QRN143J-0R0X	C R	0.0Ω	1/4W J
L1701-02	QQL244K-100Z	COIL	10μH	K
L1731	QQL244J-5R6Z	COIL	5.6μH	J
L1951	QQLZ034-460	CHOKE COIL	46μH	
L1953-54	QQL244J-5R6Z	COIL	5.6μH	J
<b>DIODE</b>				
D1101	DAN235K-X	SI.DIODE		
D1351	MA111-X	SI.DIODE		
D1356	MA111-X	SI.DIODE		
D1357	RGP10J-5025-T3	SI.DIODE		
D1358	RGP10J-5025-T3	SI.DIODE		
D1359	RGP10J-5025-T3	SI.DIODE		
D1360	MA3075/M/-X	ZENER DIODE		
D1401	RGP10J-5025-T3	SI.DIODE		
D1402	MTZJ75-T2	ZENER DIODE		
D1405	1N4003-T2	SI.DIODE		
D1408	MA111-X	SI.DIODE		

△ Symbol No.	Part No.	Part Name	Description	Local	△ Symbol No.	Part No.	Part Name	Description	Local
<b>DIODE</b>					<b>IC</b>				
D1480	MTZJ4.3A-T2	ZENER DIODE			IC1351	TDA6107Q/N2	I.C(MONO-ANA)		
D1521	ERB06-15-F1	SI.DIODE			IC1401	AN5522	I.C(MONO-ANA)		
D1522	RU3AM-LFC4	SI.DIODE			IC1480	UPC358G2-XE	I.C(MONO-ANA)		
D1523	RGP10J-5025-T3	SI.DIODE			IC1601	MSP3415D-QG-B3X	I.C(MONO-ANA)		
D1541	RGP10J-5025-T3	SI.DIODE			IC1650	AN5276	I.C(MONO-ANA)		
D1550	MA111-X	SI.DIODE			IC1665	BA4558F-X	I.C(MONO-ANA)		
D1551	RGP10J-5025-T3	SI.DIODE			IC1701	TDA9365N13S0518	I.C(MICRO-COMP)		
D1553	RGP10J-5025-T3	SI.DIODE			IC1702	AT24C08-21LS	I.C(MEMORY-OTH)	(SERVICE)	
D1554	RGP10J-5025-T3	SI.DIODE			IC1760	GP1U281Q	IFR DETECT UNIT		
D1592	MA3075/H/-X	ZENER DIODE			IC1801	MM1492AF	I.C(MONO-ANA)		
D1652-53	MA3330/L/-X	ZENER DIODE			IC1901	STR-F6707A/F7	I.C(HYBRID)		
D1682	MA111-X	SI.DIODE			IC1951	SE135N	I.C(HYBRID)		
D1702	MA3024-X	ZENER DIODE			IC1972	L88M33T-X	I.C(MONO-ANA)		
D1730-33	MA111-X	SI.DIODE			IC1974	BA51W12ST-V5	I.C(MONO-ANA)		
D1760	SLR-342VR-T16	L.E.D.			<b>OTHERS</b>				
D1770	MA111-X	SI.DIODE			LC30114-001C-H	L.E.D.HOLDER			
D1771	P1241-04	C.D.S.			CM35921-005-H	CDS HOLDER			
D1806-07	MTZJ12C-T2	ZENER DIODE			CF1103	TPSH6.0MB	CERAMIC FILTER		
D1901	GSIB460	DIODE			CF1104	TPS6.5MW	CERAMIC FILTER		
D1903	MTZJ12C-T2	ZENER DIODE			CF1105	TPS6.5MB	CERAMIC FILTER		
D1904	EG01C-T2	SI.DIODE			CF1106	QAX0639-001Z	CERAMIC FILTER		
D1906	EG01C-T2	SI.DIODE			CL1001	QZW0028-002	WIRE CLAMP		
D1907	MA3300/M/-X	CHIP ZENER DIODE			△ CP1951	ICP-N75-Y	I.C.PROTECT		
D1908	MTZJ27B-T2	ZENER DIODE			△ CP1953	ICP-N38-Y	I.C.PROTECT		
D1909	MA111-X	SI.DIODE			△ F1901	QMF51E2-4R0J4	FUSE		
D1910	NRSA63J-0R0X	MG R	0.0Ω	1/16W J	FC1901	CEMG002-001Z	FUSE CLIP		
D1911	RGP10J-TS-T3	SI.DIODE			J1770	QNS0155-001	JACK		
D1912	1SS133-T2	SI.DIODE			J1771	QNN0282-003	PIN JACK		
D1914	ERC30-02L38	SI.DIODE			J1772	QNN0282-002	PIN JACK		
D1952	ERC30-02L38	SI.DIODE			J1773	QNN0282-001	PIN JACK		
D1954	RGP30B-F1	SI.DIODE			J1801	QNN0349-001	PIN JACK		
D1955	1SR35-400A-T2	SI.DIODE			J1802	QNN0349-002	PIN JACK		
D1956	RU3AM-LFC4	SI.DIODE			J1803	QNN0348-001	PIN JACK		
D1958	MTZJ5.1A-T2	ZENER DIODE			J1804	QNN0349-001	PIN JACK		
D1964	MA3330/L/-X	ZENER DIODE			K1951	QQR1214-001Y	FERRITE BEADS		
D1965	1SS133-T2	SI.DIODE			K1954-55	QQR1214-001Y	FERRITE BEADS		
D1966	MA3068/M/-X	ZENER DIODE			LC1601	CE42482-103Y	EMI FILTER		
D1968-69	MA111-X	SI.DIODE			△ LF1901	QQR0673-004	LINE FILTER		
<b>TRANSISTOR</b>					△ LF1902	QQR1035-002	LINE FILTER		
Q1101	2SC5083/L-P/-T	SI.TRANSISTOR			△ PC1901	PC123F2	I.C(PH.COUPLER)		
Q1102-03	DTC124EKA-X	DIGI.TRANSISTOR			△ RY1901	QSK0061-001	RELAY		
Q1104	2SA1037AK/QR/-X	SI.TRANSISTOR			S1780	QSW0619-003Z	PUSH SWITCH	MENU	
Q1105-06	DTC124EKA-X	DIGI.TRANSISTOR			S1781	QSW0619-003Z	PUSH SWITCH	CH-	
Q1107	2SA1037AK/QR/-X	SI.TRANSISTOR			S1782	QSW0619-003Z	PUSH SWITCH	CH+	
Q1108	2SC2412K/QR/-X	SI.TRANSISTOR			S1783	QSW0619-003Z	PUSH SWITCH	VOL-	
Q1109	2SA1037AK/QR/-X	SI.TRANSISTOR			S1784	QSW0619-003Z	PUSH SWITCH	VOL+	
Q1110	DTC124EKA-X	DIGI.TRANSISTOR			△ S1901	QSW0846-001	PUSH SWITCH	POWER	
Q1111	2SC2412K/QR/-X	SI.TRANSISTOR			SF1101	QAX0663-001	SAW FILTER		
Q1150	2SC2412K/QR/-X	SI.TRANSISTOR			SF1102	QAX0594-001	SAW FILTER		
Q1301-02	2SA1037AK/QR/-X	SI.TRANSISTOR			SG1301-03	QAF0006-501	ARRESTER		
Q1353-55	2SC2412K/QR/-X	SI.TRANSISTOR			SG1304	QAF0041-272	ARRESTER		
Q1480	2SD1408/OY/-LB	SI.TRANSISTOR			△ SK1351	CE42446-001	C.R.T.SOCKET		
Q1521	2SC2655/Y/-T	SI.TRANSISTOR			TH1901	QAD0134-4R5	P.THERMISTOR		
Q1522	2SD2634-YD	SI.TRANSISTOR			TU1001	QAU0185-004	TUNER		
Q1591	2SA1208/ST/Z1-T	SI.TRANSISTOR			△ VA1901	QAF0052-621	VARISTOR		
Q1592	DTC124EKA-X	DIGI.TRANSISTOR			W1003	QQR1214-001Y	FERRITE BEADS		
Q1660-61	2SC2412K/QR/-X	SI.TRANSISTOR			W1008	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
Q1683-84	2SA1037AK/QR/-X	SI.TRANSISTOR			W1010	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
Q1685-86	DTC323TK-X	DIGI.TRANSISTOR			W1052	QQR1214-001Y	FERRITE BEADS		
Q1687	2SC2412K/QR/-X	SI.TRANSISTOR			W1067	QQR1214-001Y	FERRITE BEADS		
Q1701-02	2SA1037AK/QR/-X	SI.TRANSISTOR			W1071	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
Q1703	2SC2412K/QR/-X	SI.TRANSISTOR			W1096	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
Q1720	2SA1037AK/QR/-X	SI.TRANSISTOR			W1107	QQR1214-001Y	FERRITE BEADS		
Q1770	2SA1037AK/QR/-X	SI.TRANSISTOR			W1239	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
Q1801-02	DTC323TK-X	DIGI.TRANSISTOR			W1257	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
Q1803	2SA1037AK/QR/-X	SI.TRANSISTOR			W1293	QQR1214-001Y	FERRITE BEADS		
Q1804	2SC1740S/QR/-T	SI.TRANSISTOR			W1307	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
Q1860	2SC2412K/QR/-X	SI.TRANSISTOR			W1309	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
Q1861-62	2SA1037AK/QR/-X	SI.TRANSISTOR			W1318	QQR1214-001Y	FERRITE BEADS		
Q1952-54	2SC2412K/QR/-X	SI.TRANSISTOR			W1321-22	NRSA63J-0R0X	MG R	0.0Ω	1/16W J
					W1325-26	NRSA63J-0R0X	MG R	0.0Ω	1/16W J

△ Symbol No.	Part No.	Part Name	Description	Local
<b>OTHERS</b>				
W1330	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1333	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1375	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1379	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1388	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1418	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1420	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1424	QQR1214-001Y	FERRITE BEADS		
W1430	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
X1601	CE42546-001Z	CRYSTAL		
X1701	QAX0688-001	CRYSTAL		
Y1004	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
Y1103	QRE141J-0R0Y	C R	0.0Ω 1/4W	J
Y1301-02	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
Y1602	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
Y1604	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J

## REMOTE CONTROL UNIT PARTS LIST (RM-C352-1C)

△ Ref.No.	Part No.	Part Name	Description	Local
	31392340128	BATTERY COVER		

# PRINTED WIRING BOARD PARTS LIST (AV-21LX/C)

## MAIN PW BOARD ASS'Y (SCH-1060A-H2)

△	Symbol No.	Part No.	Part Name	Description	Local	△	Symbol No.	Part No.	Part Name	Description	Local
<b>RESISTOR</b>						<b>RESISTOR</b>					
	R1001-02	NRSA63J-221X	MG R	220Ω 1/16W J			R1484-85	NRSA63J-562X	MG R	5.6kΩ 1/16W J	
	R1003	NRSA63J-392X	MG R	3.9kΩ 1/16W J			R1486	NRSA63J-272X	MG R	2.7kΩ 1/16W J	
	R1004	NRSA63J-221X	MG R	220Ω 1/16W J			R1487	NRSA63J-333X	MG R	33kΩ 1/16W J	
	R1006	NRSA63J-273X	MG R	27kΩ 1/16W J			R1489	NRSA63J-122X	MG R	1.2kΩ 1/16W J	
	R1101	NRSA63J-100X	MG R	10Ω 1/16W J			R1490	NRSA63J-102X	MG R	1kΩ 1/16W J	
	R1102	NRSA63J-682X	MG R	6.8kΩ 1/16W J			R1491	NRSA63J-562X	MG R	5.6kΩ 1/16W J	
	R1103	NRSA63J-272X	MG R	2.7kΩ 1/16W J			R1492	NRSA63J-822X	MG R	8.2kΩ 1/16W J	
	R1104	NRSA63J-181X	MG R	180Ω 1/16W J			R1493	QRE121J-223Y	C R	22kΩ 1/2W J	
	R1105	NRSA63J-220X	MG R	22Ω 1/16W J			R1494	QRL03EJ-330X	OM R	33Ω 3W J	
	R1106	NRSA63J-101X	MG R	100Ω 1/16W J			R1521	NRSA63J-101X	MG R	100Ω 1/16W J	
	R1107	NRSA63J-472X	MG R	4.7kΩ 1/16W J			R1522	NRSA63J-102X	MG R	1kΩ 1/16W J	
	R1108-09	NRSA63J-222X	MG R	2.2kΩ 1/16W J			R1524	QRL02EJ-270X	OM R	27Ω 2W J	
	R1111	NRSA63J-102X	MG R	1kΩ 1/16W J			R1526	QRG01GJ-271	OM R	270Ω 1W J	
	R1112	NRSA63J-103X	MG R	10kΩ 1/16W J			R1527	QRL03EJ-103X	OM R	10kΩ 3W J	
	R1113	NRSA63J-271X	MG R	270Ω 1/16W J			R1528-29	QRX029J-1R2	MF R	1.2Ω 2W J	
	R1114	NRSA63J-821X	MG R	820Ω 1/16W J			R1531	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
	R1115	NRSA63J-181X	MG R	180Ω 1/16W J		△	R1532	QRZ9017-4R7	F R	4.7Ω 1/4W J	
	R1117	NRSA63J-102X	MG R	1kΩ 1/16W J		△	R1540	QRZ9011-4R7	F R	4.7Ω 1/2W J	
	R1119	NRSA63J-102X	MG R	1kΩ 1/16W J			R1541-42	QRE121J-154Y	C R	150kΩ 1/2W J	
	R1120	NRSA63J-471X	MG R	470Ω 1/16W J			R1543	QRE121J-471Y	C R	470Ω 1/2W J	
	R1130	NRSA63J-472X	MG R	4.7kΩ 1/16W J			R1545	QRE121J-220Y	C R	22Ω 1/2W J	
	R1131	NRSA63J-471X	MG R	470Ω 1/16W J			R1546	QRE121J-822Y	C R	8.2kΩ 1/2W J	
	R1132	NRSA63J-222X	MG R	2.2kΩ 1/16W J			R1591	QRE121J-222Y	C R	2.2kΩ 1/2W J	
	R1133	NRSA63J-152X	MG R	1.5kΩ 1/16W J			R1592	QRZ0221-2R2	UNF R	2.2Ω	
	R1134	NRSA63J-182X	MG R	1.8kΩ 1/16W J			R1593	NRSA63J-102X	MG R	1kΩ 1/16W J	
	R1135	NRSA63J-561X	MG R	560Ω 1/16W J			R1594	QRE121J-183Y	C R	18kΩ 1/2W J	
	R1136	NRSA63J-472X	MG R	4.7kΩ 1/16W J			R1595	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
	R1137	NRSA63J-103X	MG R	10kΩ 1/16W J			R1621-22	NRSA63J-101X	MG R	100Ω 1/16W J	
	R1138	NRSA63J-561X	MG R	560Ω 1/16W J			R1626	NRSA63J-472X	MG R	4.7kΩ 1/16W J	
	R1139	NRSA63J-222X	MG R	2.2kΩ 1/16W J			R1627	NRSA63J-224X	MG R	220kΩ 1/16W J	
	R1140	NRSA63J-152X	MG R	1.5kΩ 1/16W J			R1628	NRSA63J-104X	MG R	100kΩ 1/16W J	
	R1141	NRSA63J-182X	MG R	1.8kΩ 1/16W J			R1629	NRSA63J-153X	MG R	15kΩ 1/16W J	
	R1142	NRSA63J-561X	MG R	560Ω 1/16W J			R1630	NRSA63J-273X	MG R	27kΩ 1/16W J	
	R1143	NRSA63J-471X	MG R	470Ω 1/16W J			R1631	NRSA63J-473X	MG R	47kΩ 1/16W J	
	R1144	NRSA63J-220X	MG R	22Ω 1/16W J			R1632-33	NRSA63J-103X	MG R	10kΩ 1/16W J	
	R1145	NRSA63J-821X	MG R	820Ω 1/16W J			R1650-51	NRSA63J-392X	MG R	3.9kΩ 1/16W J	
	R1146	NRSA63J-103X	MG R	10kΩ 1/16W J			R1652-53	NRSA63J-0R0X	MG R	0.0Ω 1/16W J	
	R1147	NRSA63J-101X	MG R	100Ω 1/16W J			R1654-55	NRSA63J-392X	MG R	3.9kΩ 1/16W J	
	R1148	NRSA63J-332X	MG R	3.3kΩ 1/16W J			R1658-59	QRE121J-2R2Y	C R	2.2Ω 1/2W J	
	R1149	NRSA63J-122X	MG R	1.2kΩ 1/16W J			R1660	NRSA63J-103X	MG R	10kΩ 1/16W J	
	R1301-02	NRSA63J-222X	MG R	2.2kΩ 1/16W J			R1661	NRSA63J-683X	MG R	68kΩ 1/16W J	
	R1303	NRSA63J-562X	MG R	5.6kΩ 1/16W J			R1662	NRSA63J-333X	MG R	33kΩ 1/16W J	
	R1304-05	NRSA63J-222X	MG R	2.2kΩ 1/16W J			R1663	NRSA63J-103X	MG R	10kΩ 1/16W J	
	R1306	NRSA63J-562X	MG R	5.6kΩ 1/16W J			R1664	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
	R1350-51	NRSA63J-151X	MG R	150Ω 1/16W J			R1688	NRSA63J-273X	MG R	27kΩ 1/16W J	
	R1353	NRSA63J-151X	MG R	150Ω 1/16W J			R1690	NRSA63J-104X	MG R	100kΩ 1/16W J	
	R1354	QRE121J-222Y	C R	2.2kΩ 1/2W J			R1691	NRSA63J-682X	MG R	6.8kΩ 1/16W J	
	R1363	QRZ0107-152Z	C R	1.5kΩ 1/2W K			R1692	NRSA63J-104X	MG R	100kΩ 1/16W J	
	R1364	QRE121J-222Y	C R	2.2kΩ 1/2W J			R1693	NRSA63J-103X	MG R	10kΩ 1/16W J	
	R1365	QRZ0107-152Z	C R	1.5kΩ 1/2W K			R1694	NRSA63J-472X	MG R	4.7kΩ 1/16W J	
	R1366	QRZ0107-474Z	C R	470kΩ 1/2W K			R1695	NRSA63J-562X	MG R	5.6kΩ 1/16W J	
	R1368	QRZ0107-152Z	C R	1.5kΩ 1/2W K			R1696	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
	R1369	QRE121J-222Y	C R	2.2kΩ 1/2W J			R1698-99	NRSA63J-104X	MG R	100kΩ 1/16W J	
	R1373	QRE121J-394Y	C R	390kΩ 1/2W J			R1701	NRSA63J-103X	MG R	10kΩ 1/16W J	
	R1374	QRE121J-124Y	C R	120kΩ 1/2W J			R1702-03	NRSA63J-101X	MG R	100Ω 1/16W J	
	R1380-83	NRSA63J-101X	MG R	100Ω 1/16W J			R1704-06	NRSA63J-102X	MG R	1kΩ 1/16W J	
	R1384	NRSA63J-223X	MG R	22kΩ 1/16W J			R1707-10	NRSA63J-472X	MG R	4.7kΩ 1/16W J	
	R1401	NRSA63J-224X	MG R	220kΩ 1/16W J			R1711-14	NRSA63J-101X	MG R	100Ω 1/16W J	
	R1403	NRSA63J-0R0X	MG R	0.0Ω 1/16W J			R1715-17	NRSA63J-103X	MG R	10kΩ 1/16W J	
	R1405	NRSA63J-682X	MG R	6.8kΩ 1/16W J			R1718-19	NRSA63J-221X	MG R	220Ω 1/16W J	
	R1406	NRSA63J-123X	MG R	12kΩ 1/16W J			R1720	NRSA63J-102X	MG R	1kΩ 1/16W J	
	R1408	NRSA63J-682X	MG R	6.8kΩ 1/16W J			R1721-24	NRSA63J-221X	MG R	220Ω 1/16W J	
	R1410	NRSA63J-123X	MG R	12kΩ 1/16W J			R1725	NRSA63J-103X	MG R	10kΩ 1/16W J	
	R1411	QRG01GJ-221	OM R	220Ω 1W J			R1726	NRSA63J-472X	MG R	4.7kΩ 1/16W J	
	R1412	QRE121J-1R0Y	C R	1.0Ω 1/2W J			R1727	NRSA63J-104X	MG R	100kΩ 1/16W J	
	R1413	QRX01GJ-5R6	MF R	5.6Ω 1W J			R1728	NRSA63J-103X	MG R	10kΩ 1/16W J	
	R1414	QRE121J-6R8Y	C R	6.8Ω 1/2W J			R1730	NRSA63J-223X	MG R	22kΩ 1/16W J	
	R1425	NRSA63J-683X	MG R	68kΩ 1/16W J			R1731	NRSA63J-101X	MG R	100Ω 1/16W J	
	R1480	QRE121J-681Y	C R	680Ω 1/2W J			R1732	NRSA02F-393X	MG R	39kΩ 1/10W F	
	R1481	NRSA63J-223X	MG R	22kΩ 1/16W J			R1733	NRSA63J-273X	MG R	27kΩ 1/16W J	
	R1482	NRSA63J-562X	MG R	5.6kΩ 1/16W J			R1734	NRSA63J-391X	MG R	390Ω 1/16W J	
	R1483	NRSA63J-823X	MG R	82kΩ 1/16W J			R1735	NRSA63J-104X	MG R	100kΩ 1/16W J	

△ Symbol No.	Part No.	Part Name	Description	Local
<b>RESISTOR</b>				
R1736	NRSA63J-333X	MG R	33kΩ 1/16W J	
R1737	NRSA63J-272X	MG R	2.7kΩ 1/16W J	
R1738	NRSA63J-103X	MG R	10kΩ 1/16W J	
R1739-41	NRSA63J-101X	MG R	100Ω 1/16W J	
R1742	NRSA63J-0R0X	MG R	0.0Ω 1/16W J	
R1743	QRE141J-102Y	C R	1kΩ 1/4W J	
R1744	NRSA63J-561X	MG R	560Ω 1/16W J	
R1745	NRSA63J-105X	MG R	1MΩ 1/16W J	
R1746	NRSA63J-333X	MG R	33kΩ 1/16W J	
R1747	NRSA63J-103X	MG R	10kΩ 1/16W J	
R1748-49	NRSA02J-475X	MG R	4.7MΩ 1/10W J	
R1750-51	QRE141J-0R0Y	C R	0.0Ω 1/4W J	
R1755-56	NRSA63J-101X	MG R	100Ω 1/16W J	
R1757-58	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
R1760	NRSA63J-682X	MG R	6.8kΩ 1/16W J	
R1770	QRE121J-271Y	C R	270Ω 1/2W J	
R1771	NRSA63J-102X	MG R	1kΩ 1/16W J	
R1772	QRE121J-271Y	C R	270Ω 1/2W J	
R1773	NRSA63J-102X	MG R	1kΩ 1/16W J	
R1775	NRSA63J-332X	MG R	3.3kΩ 1/16W J	
R1776	NRSA63J-392X	MG R	3.9kΩ 1/16W J	
R1777	NRSA63J-682X	MG R	6.8kΩ 1/16W J	
R1779	NRSA63J-272X	MG R	2.7kΩ 1/16W J	
R1780	NRSA63J-471X	MG R	470Ω 1/16W J	
R1781	NRSA63J-122X	MG R	1.2kΩ 1/16W J	
R1782	NRSA63J-181X	MG R	180Ω 1/16W J	
R1783	NRSA63J-221X	MG R	220Ω 1/16W J	
R1784	NRSA63J-331X	MG R	330Ω 1/16W J	
R1785	NRSA63J-471X	MG R	470Ω 1/16W J	
R1803	NRSA63J-333X	MG R	33kΩ 1/16W J	
R1805	NRSA63J-750X	MG R	75Ω 1/16W J	
R1808	NRSA63J-823X	MG R	82kΩ 1/16W J	
R1809	NRSA63J-391X	MG R	390Ω 1/16W J	
R1810	NRSA63J-823X	MG R	82kΩ 1/16W J	
R1811	NRSA63J-391X	MG R	390Ω 1/16W J	
R1812	NRSA63J-104X	MG R	100kΩ 1/16W J	
R1813	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
R1815	NRSA63J-101X	MG R	100Ω 1/16W J	
R1818	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
R1820	NRSA63J-101X	MG R	100Ω 1/16W J	
R1821	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
R1823	NRSA63J-101X	MG R	100Ω 1/16W J	
R1824	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
R1826	NRSA63J-101X	MG R	100Ω 1/16W J	
R1829	NRSA63J-750X	MG R	75Ω 1/16W J	
R1830-31	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
R1832	NRSA63J-122X	MG R	1.2kΩ 1/16W J	
R1833	NRSA63J-102X	MG R	1kΩ 1/16W J	
R1834-35	NRSA63J-562X	MG R	5.6kΩ 1/16W J	
R1836	NRSA63J-750X	MG R	75Ω 1/16W J	
R1837	NRSA63J-101X	MG R	100Ω 1/16W J	
R1838	QRK126J-121X	C R	120Ω 1/2W J	
R1839-40	QRE121J-221Y	C R	220Ω 1/2W J	
R1841-42	NRSA63J-0R0X	MG R	0.0Ω 1/16W J	
R1843	NRSA63J-821X	MG R	820Ω 1/16W J	
R1844	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
R1845	NRSA63J-102X	MG R	1kΩ 1/16W J	
R1846	NRSA63J-222X	MG R	2.2kΩ 1/16W J	
R1847	NRSA63J-103X	MG R	10kΩ 1/16W J	
R1848	NRSA63J-471X	MG R	470Ω 1/16W J	
R1849	NRSA63J-221X	MG R	220Ω 1/16W J	
R1880	NRSA63J-202X	MG R	2kΩ 1/16W J	
R1881	NRSA63J-103X	MG R	10kΩ 1/16W J	
R1882	NRSA63J-471X	MG R	470Ω 1/16W J	
R1883	NRSA63J-181X	MG R	180Ω 1/16W J	
R1884-85	QRE141J-750Y	C R	75Ω 1/4W J	
R1898	QRE141J-750Y	C R	75Ω 1/4W J	
R1902	QRF154K-2R2	UNF R	2.2Ω 15W K	
R1904	QRE121J-681Y	C R	680Ω 1/2W J	
R1905	QRM034J-R22	MP R	0.22Ω 3W J	
R1907	NRSA63J-563X	MG R	56kΩ 1/16W J	
R1908	QRL039J-333	OM R	33kΩ 3W J	

△ Symbol No.	Part No.	Part Name	Description	Local
<b>RESISTOR</b>				
R1909	QRE121J-474Y	C R	470kΩ 1/2W J	
R1910	QRE121J-392Y	C R	3.9kΩ 1/2W J	
R1911	QRE121J-332Y	C R	3.3kΩ 1/2W J	
R1912	NRSA63J-182X	MG R	1.8kΩ 1/16W J	
△ R1915	QRZ0111-474	C R	470kΩ 1/2W K	
R1952	NRSA63J-332X	MG R	3.3kΩ 1/16W J	
R1953	NRSA63J-101X	MG R	100Ω 1/16W J	
R1954	QRE121J-560Y	C R	56Ω 1/2W J	
R1955	QRG01GJ-330	OM R	33Ω 1W J	
R1956	QRE121J-100Y	C R	10Ω 1/2W J	
R1957	QRE121J-6R8Y	C R	6.8Ω 1/2W J	
R1960	NRSA63J-391X	MG R	390Ω 1/16W J	
R1961	QRL02EJ-223X	OM R	22kΩ 2W J	
R1962	NRSA63J-561X	MG R	560Ω 1/16W J	
R1963	QRE121J-103Y	C R	10kΩ 1/2W J	
R1964	NRSA63J-473X	MG R	47kΩ 1/16W J	
R1965	NRSA63J-0R0X	MG R	0.0Ω 1/16W J	
R1966	NRSA63J-682X	MG R	6.8kΩ 1/16W J	
R1967	NRSA63J-473X	MG R	47kΩ 1/16W J	
R1970	NRSA63J-153X	MG R	15kΩ 1/16W J	
R1971	NRSA63J-183X	MG R	18kΩ 1/16W J	
△ R1991	QRZ0057-825	C R	8.2MΩ 1W J	
<b>CAPACITOR</b>				
C1001	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1002	QETN1HM-106Z	E CAP.	10μF 50V M	
C1003	QFV71HJ-104Z	MF CAP.	0.1μF 50V J	
C1004	QETN1CM-477Z	E CAP.	470μF 16V M	
C1005	NCB31HK-222X	C CAP.	2200pF 50V K	
C1006	QETN1CM-336Z	E CAP.	33μF 16V M	
C1007	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1101-05	NCB31HK-472X	C CAP.	4700pF 50V K	
C1106-07	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1109	QETN1HM-106Z	E CAP.	10μF 50V M	
C1130-32	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1133	QETN1CM-107Z	E CAP.	100μF 16V M	
C1134	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1135	QETN1EM-476Z	E CAP.	47μF 25V M	
C1136-38	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1140-42	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1143	QETN1HM-106Z	E CAP.	10μF 50V M	
C1144	NCB31HK-223X	C CAP.	0.022μF 50V K	
C1308	NCB31HK-103X	C CAP.	0.01μF 50V K	
C1352	QFK62EK-104Z	MM CAP.	0.1μF 250V K	
C1353	QETN2EM-475Z	E CAP.	4.7μF 250V M	
C1354	QCZ0131-222	C CAP.	2200pF 2000V K	
C1355	QCZ0131-472	C CAP.	4700pF 2000V K	
C1357	NDC31HJ-101X	C CAP.	100pF 50V J	
C1358	QETN1CM-477Z	E CAP.	470μF 16V M	
C1401	QETN1HM-105Z	E CAP.	1μF 50V M	
C1402	QCB31HK-682Z	C CAP.	6800pF 50V K	
C1403	QEHR1VM-227Z	E CAP.	220μF 35V M	
C1406	QFLC2AJ-683Z	M CAP.	0.068μF 100V J	
C1408	QFV71HJ-184Z	MF CAP.	0.18μF 50V J	
C1411-12	NCF21HZ-334X	C CAP.	0.33μF 50V Z	
C1413	QFLC2AJ-563Z	M CAP.	0.056μF 100V J	
C1422	QETN1VM-108Z	E CAP.	1000μF 35V M	
C1480	QETN1HM-106Z	E CAP.	10μF 50V M	
C1483	QEZ0195-475Z	E CAP.	4.7μF 50V M	
C1485	QETN1HM-226Z	E CAP.	22μF 50V M	
C1521	QETN1VM-476Z	E CAP.	47μF 35V M	
C1522	QFLC1HJ-332Z	M CAP.	3300pF 50V J	
C1523	QFLC1HJ-223Z	M CAP.	0.022μF 50V J	
C1524	QFZ0196-602	MPP CAP.	6000pF 1.5kVH ±3%	
C1525	QFZ0196-472	MPP CAP.	4700pF 1.5kVH ±3%	
C1526	QFP32GJ-183	PP CAP.	0.018μF 400V J	
C1527-28	QFZ0199-154	MPP CAP.	0.15μF 250V J	
C1529	QEHR2EM-475Z	E CAP.	4.7μF 250V M	
C1530	QCB32HK-561Z	C CAP.	560pF 500V K	
C1531	QEHR1EM-108Z	E CAP.	1000μF 25V M	
C1533	QEHR1EM-108Z	E CAP.	1000μF 25V M	
C1535	QCB32HK-101Z	C CAP.	100pF 500V K	

△	Symbol No.	Part No.	Part Name	Description	Local	△	Symbol No.	Part No.	Part Name	Description	Local	
<b>CAPACITOR</b>						<b>CAPACITOR</b>						
	C1536	QFLC1HJ-103Z	M CAP.	0.01μF 50V	J		C1812	NCF31AZ-105X	C CAP.	1μF 10V	Z	
	C1540	QFV71HJ-104Z	MF CAP.	0.1μF 50V	J		C1813	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	C1541	QETN2EM-106Z	E CAP.	10μF 250V	M		C1814	QFLC1HJ-104Z	M CAP.	0.1μF 50V	J	
	C1550	NCB31CK-104X	C CAP.	0.1μF 16V	K		C1815	NCF31AZ-105X	C CAP.	1μF 10V	Z	
	C1591	QETN1AM-107Z	E CAP.	100μF 10V	M		C1817	NCF31AZ-105X	C CAP.	1μF 10V	Z	
	C1592	QEZO203-107	E CAP.	100μF 160V	M		C1819	QFLC1HJ-104Z	M CAP.	0.1μF 50V	J	
	C1593	QETN1EM-476Z	E CAP.	47μF 25V	M		C1820-21	NCF31AZ-105X	C CAP.	1μF 10V	Z	
	C1603	QETN1CM-228Z	E CAP.	2200μF 16V	M		C1822	QETN1CM-477Z	E CAP.	470μF 16V	M	
	C1625	QETN1HM-106Z	E CAP.	10μF 50V	M		C1823-24	QETN1CM-107Z	E CAP.	100μF 16V	M	
	C1626	QETN1CM-107Z	E CAP.	100μF 16V	M		C1825	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	C1629	QETN1HM-475Z	E CAP.	4.7μF 50V	M		C1826	QFLC1HJ-104Z	M CAP.	0.1μF 50V	J	
	C1630	NDC31HJ-471X	C CAP.	470pF 50V	J		C1827	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	C1631	NCB31EK-333X	C CAP.	0.033μF 25V	K		C1829-31	NCB31HK-103X	C CAP.	0.01μF 50V	K	
	C1634	QETN1HM-106Z	E CAP.	10μF 50V	M		C1833	QETN1HM-226Z	E CAP.	22μF 50V	M	
	C1636-37	QETN1HM-105Z	E CAP.	1μF 50V	M		C1834	NDC31HJ-181X	C CAP.	180pF 50V	J	
	C1638	NCB31EK-333X	C CAP.	0.033μF 25V	K	△	C1901	QFZ9073-104	MF CAP.	0.1μF		
	C1639	NDC31HJ-471X	C CAP.	470pF 50V	J	△	C1902	QFZ9073-473	C CAP.	0.047μF		
	C1640	QETN1HM-475Z	E CAP.	4.7μF 50V	M		C1903-05	QCZ9015-102Z	C CAP.	1000pF 250V	Z	
	C1641	QETN1CM-107Z	E CAP.	100μF 16V	M	△	C1906	QFZ9073-224	MF CAP.	0.22μF		
	C1642	NCB31CK-104X	C CAP.	0.1μF 16V	K		C1907	QEZO199-227	E CAP.	220μF 400V	M	
	C1643	NCB31HK-562X	C CAP.	5600pF 50V	K		C1908	QCZO364-222	C CAP.	2200pF		
	C1644	QETN1HM-475Z	E CAP.	4.7μF 50V	M		C1910	NDC21HJ-471X	C CAP.	470pF 50V	J	
	C1645-46	QETN1HM-106Z	E CAP.	10μF 50V	M		C1911	QETN1EM-227Z	E CAP.	220μF 25V	M	
	C1647	NCB31EK-393X	C CAP.	0.039μF 25V	K		C1914	QETN1EM-227Z	E CAP.	220μF 25V	M	
	C1648	NCB31HK-223X	C CAP.	0.022μF 50V	K		C1915	QFLC1HJ-222Z	M CAP.	2200pF 50V	J	
	C1650	QEHR1HM-106Z	E CAP.	10μF 50V	M		C1952	QCB32HK-471Z	C CAP.	470pF 500V	K	
	C1651	QETN1HM-107Z	E CAP.	100μF 50V	M		C1953	QEHR1VM-108Z	E CAP.	1000μF 35V	M	
	C1652	QETN1HM-106Z	E CAP.	10μF 50V	M		C1954	NCB31HK-102X	C CAP.	1000pF 50V	K	
	C1655-56	QETM1VM-108	E CAP.	1000μF 35V	M		C1957	QCB32HK-471Z	C CAP.	470pF 500V	K	
	C1659-61	NCF21HZ-224X	C CAP.	0.22μF 50V	Z		C1958	QETN1CM-108Z	E CAP.	1000μF 16V	M	
	C1662	QETN1HM-106Z	E CAP.	10μF 50V	M		C1959	QCZO364-561	C CAP.	560pF		
	C1663	NCF21HZ-224X	C CAP.	0.22μF 50V	Z		C1960	QEZO203-107	E CAP.	100μF 160V	M	
	C1665	NCF31AZ-105X	C CAP.	1μF 10V	Z		C1962	QETN1HM-106Z	E CAP.	10μF 50V	M	
	C1669	NCF31AZ-105X	C CAP.	1μF 10V	Z		C1963	QETN1CM-476Z	E CAP.	47μF 16V	M	
	C1681-82	QETN1CM-227Z	E CAP.	220μF 16V	M		C1964	QEHR1VM-476Z	E CAP.	47μF 35V	M	
	C1683	QETM1CM-336Z	E CAP.	33μF 16V	M		C1968	NCB31CK-104X	C CAP.	0.1μF 16V	K	
	C1684	QETN1HM-106Z	E CAP.	10μF 50V	M		C1972	QETN1HM-476Z	E CAP.	47μF 50V	M	
	C1685-86	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J		C1973	QETN1AM-107Z	E CAP.	100μF 10V	M	
	C1702	QETN1HM-106Z	E CAP.	10μF 50V	M		C1974	NCB31CK-104X	C CAP.	0.1μF 16V	K	
	C1703-04	NDC31HJ-220X	C CAP.	22pF 50V	J		C1975	QETN1CM-227Z	E CAP.	220μF 16V	M	
	C1706	NCB21EK-224X	C CAP.	0.22μF 25V	K		C1976	QETN1AM-107Z	E CAP.	100μF 10V	M	
	C1707	QETN1CM-107Z	E CAP.	100μF 16V	M		C1977	QETN1AM-477Z	E CAP.	470μF 10V	M	
	C1709	QETN1CM-107Z	E CAP.	100μF 16V	M		C1978	NCB21HK-104X	C CAP.	0.1μF 50V	K	
	C1710	NCB21EK-224X	C CAP.	0.22μF 25V	K		C1980	QETN1CM-107Z	E CAP.	100μF 16V	M	
	C1711	NCB31CK-104X	C CAP.	0.1μF 16V	K		△	C1991-93	QCZ9079-102	C CAP.		
	C1713	NCB31CK-104X	C CAP.	0.1μF 16V	K							
	C1714	QETN1CM-476Z	E CAP.	47μF 16V	M							
	C1720	QETN1CM-476Z	E CAP.	47μF 16V	M							
	C1725	NCB31HK-681X	C CAP.	680pF 50V	K							
	C1726	QETN1HM-106Z	E CAP.	10μF 50V	M							
	C1730-31	NCB21EK-224X	C CAP.	0.22μF 25V	K							
	C1732	QETN1CM-107Z	E CAP.	100μF 16V	M							
	C1733	NCB31CK-104X	C CAP.	0.1μF 16V	K							
	C1734-35	NCB31HK-222X	C CAP.	2200pF 50V	K							
	C1736-37	QETN1HM-105Z	E CAP.	1μF 50V	M							
	C1738	NCB31CK-104X	C CAP.	0.1μF 16V	K							
	C1739	NFV41CJ-104X	MPP CAP.	0.1μF 16V	J							
	C1740	QETN1HM-225Z	E CAP.	2.2μF 50V	M							
	C1741-42	NCB31CK-104X	C CAP.	0.1μF 16V	K							
	C1743	QETN1CM-107Z	E CAP.	100μF 16V	M							
	C1744	NCB21HK-102X	C CAP.	1000pF 50V	K							
	C1745-47	NCB31EK-473X	C CAP.	0.047μF 25V	K							
	C1749	QETN1HM-106Z	E CAP.	10μF 50V	M							
	C1751-53	NCB31CK-104X	C CAP.	0.1μF 16V	K							
	C1760	NCB21EK-104X	C CAP.	0.1μF 25V	K							
	C1761	QETN1CM-107Z	E CAP.	100μF 16V	M							
	C1770	QETN1HM-106Z	E CAP.	10μF 50V	M							
	C1801-04	QETN1HM-106Z	E CAP.	10μF 50V	M							
	C1805	QFLC1HJ-104Z	M CAP.	0.1μF 50V	J							
	C1807-08	NCF31AZ-105X	C CAP.	1μF 10V	Z							
	C1810	NCF31AZ-105X	C CAP.	1μF 10V	Z							
	C1811	QFLC1HJ-104Z	M CAP.	0.1μF 50V	J							
<b>TRANSFORMER</b>						<b>TRANSFORMER</b>						
	T1521	CE40203-00CJ1		DRIVE TRANSF.			T1521	CE40203-00CJ1		DRIVE TRANSF.		
	△	T1551	QQH0104-001	H.V.TRANSF.			△	T1551	QQH0104-001	H.V.TRANSF.		
	△	T1901	QQS0117-001	SWTICH.TRANSF.			△	T1901	QQS0117-001	SWTICH.TRANSF.		
<b>COIL</b>						<b>COIL</b>						
	L1001-02	QQL244K-8R2Z		COIL			L1001-02	QQL244K-8R2Z		COIL	8.2μH	K
	L1101-02	QQL244J-5R6Z		COIL			L1101-02	QQL244J-5R6Z		COIL	5.6μH	J
	L1103	QQL244K-100Z		COIL			L1103	QQL244K-100Z		COIL	10μH	K
	L1104	QQL244K-180Z		COIL			L1104	QQL244K-180Z		COIL	18μH	K
	L1351	QQL03BJ-5R6Z		COIL			L1351	QQL03BJ-5R6Z		COIL	5.6μH	J
	L1480	QQLZ016-821		CHOKO COIL			L1480	QQLZ016-821		CHOKO COIL	820μH	
	L1523	QQR1005-002		LNINARIITY COIL			L1523	QQR1005-002		LNINARIITY COIL		
	L1524	QQLZ034-430		CHOKO COIL			L1524	QQLZ034-430		CHOKO COIL	43μH	
	L1701-02	QQL244K-100Z		COIL			L1701-02	QQL244K-100Z		COIL	10μH	K
	L1731	QQL244J-5R6Z		COIL			L1731	QQL244J-5R6Z		COIL	5.6μH	J
	L1951	QQLZ034-460		CHOKO COIL			L1951	QQLZ034-460		CHOKO COIL	46μH	
	L1953-54	QQL244J-5R6Z		COIL			L1953-54	QQL244J-5R6Z		COIL	5.6μH	J
<b>DIODE</b>						<b>DIODE</b>						
	D1101	DAN235K-X		SI.DIODE			D1101	DAN235K-X		SI.DIODE		
	D1351	MA111-X		SI.DIODE			D1351	MA111-X		SI.DIODE		
	D1356	MA111-X		SI.DIODE			D1356	MA111-X		SI.DIODE		
	D1357	RGP10J-5025-T3		SI.DIODE			D1357	RGP10J-5025-T3		SI.DIODE		





△ Symbol No.	Part No.	Part Name	Description	Local
<b>OTHERS</b>				
TH1901	QAD0134-4R5	P.THERMISTOR		
TU1001	QAU0185-004	TUNER		
△ VA1901	QAF0052-621	VARISTOR		
W1003	QQR1214-001Y	FERRITE BEADS		
W1008	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1010	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1052	QQR1214-001Y	FERRITE BEADS		
W1067	QQR1214-001Y	FERRITE BEADS		
W1071	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1096	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1107	QQR1214-001Y	FERRITE BEADS		
W1239	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1257	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1293	QQR1214-001Y	FERRITE BEADS		
W1307	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1309	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1318	QQR1214-001Y	FERRITE BEADS		
W1321-22	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1325-26	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1330	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1333	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1375	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1379	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1388	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1418	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
W1424	QQR1214-001Y	FERRITE BEADS		
W1430	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
X1701	QAX0688-001	CRYSTAL		
Y1001-02	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
Y1103	QRE141J-0R0Y	C R	0.0Ω 1/4W	J
Y1130	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
Y1301-02	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
Y1601	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J
Y1603	NRSA63J-0R0X	MG R	0.0Ω 1/16W	J

## REMOTE CONTROL UNIT PARTS LIST (RM-C357-1C)

△ Ref.No.	Part No.	Part Name	Description	Local
	31392340128	BATTERY COVER		