


PARTS LIST

CAUTION

- The parts identified by the  symbol are important for the safety. Whenever replacing these parts, be sure to use specified ones to secure the safety.
- The parts not indicated in this Parts List and those which are filled with lines — in the Parts No. columns will not be supplied.
- P. W. Board Ass'y will not be supplied, but those which are filled with the Parts No. in the Parts No. columns will be supplied.

ABBREVIATIONS OF RESISTORS, CAPACITORS AND TOLERANCES

RESISTORS		CAPACITORS	
C R	Carbon Resistor	C CAP.	Ceramic Capacitor
F R	Fusible Resistor	E CAP.	Electrolytic Capacitor
P R	Plate Resistor	M CAP.	Mylar Capacitor
V R	Variable Resistor	HV CAP.	High Voltage Capacitor
HV R	High Voltage Resistor	MF CAP.	Metalized Film Capacitor
MF R	Metal Film Resistor	MM CAP.	Metalized Mylar Capacitor
MG R	Metal Glazed Resistor	MP CAP.	Metalized Polystyrol Capacitor
MP R	Metal Plate Resistor	PP CAP.	Polypropylene Capacitor
OM R	Metal Oxide Film Resistor	PS CAP.	Polystyrol Capacitor
CMF R	Coating Metal Film Resistor	TF CAP.	Thin Film Capacitor
UNF R	Non-Flammable Resistor	MPP CAP.	Metalized Polypropylene Capacitor
CH V R	Chip Variable Resistor	TAN. CAP.	Tantalum Capacitor
CH MG R	Chip Metal Glazed Resistor	CH C CAP.	Chip Ceramic Capacitor
COMP. R	Composition Resistor	BP E CAP.	Bi-Polar Electrolytic Capacitor
LPTC R	Linear Positive Temperature Coefficient Resistor	CH AL E CAP.	Chip Aluminum Electrolytic Capacitor
		CH AL BP CAP.	Chip Aluminum Bi-Polar Capacitor
		CH TAN. E CAP.	Chip Tantalum Electrolytic Capacitor
		CH AL BP E CAP.	Chip Tantalum Bi-Polar Electrolytic Capacitor

TOLERANCES									
F	G	J	K	M	N	R	H	Z	P
±1%	±2%	±5%	±10%	±20%	±30%	+30% -10%	+50% -10%	+80% -20%	+100% -0%

CONTENTS

■ USING PW BOARD & REMOTE CONTROL UNIT	35
■ REMOTE CONTROL UNIT PARTS LIST	35

AV-21D73_{NT}

■ EXPLODED VIEW PARTS LIST	36
■ EXPLODED VIEW (1)	36
■ EXPLODED VIEW (2)	37
■ PRINTED WIRING BOARD PARTS LIST	
● MAIN PW BOARD ASS'Y (SCG-1438A)	38
■ PACKING PARTS LIST	42
■ PACKING	43

AV-16N73_{NT}

■ EXPLODED VIEW PARTS LIST	44
■ EXPLODED VIEW (1)	44
■ EXPLODED VIEW (2)	45
■ PRINTED WIRING BOARD PARTS LIST	
● MAIN PW BOARD ASS'Y (SCG-1437A)	46
■ PACKING PARTS LIST	50
■ PACKING	51

USING PW BOARD & REMOTE CONTROL UNIT


PWB ASS'Y \ Model	AV-21D73 _{VT}	AV-16N73 _{VT}
MAIN PWB	SCG-1438A	SCG-1437A
REMOTE CONTROL UNIT	RM-C367GY-1H	←

REMOTE CONTROL UNIT PARTS LIST (RM-C367GY-1H)

(AV-21D73/VT / AV-16N73/VT)

Ref.No.	Part No.	Part Name	Description
---------	----------	-----------	-------------

	25-1168F	BATTERY COVER	
--	----------	---------------	--




AV-21D73NT


EXPLODED VIEW PARTS LIST

△ Ref.No.	Part No.	Part Name	Description
△ V01	A51JSW51X07	ITC	
△ L01	CELD029-004J6	DEG COIL	
△ T1522	QQH0070-001-KD	FBT	
△ 1	LC11129-026A-HK	FRONT CABINET	
△ 2	CM48125-009	JVC MARK	
△ 3	GG30020-001A-H	REMOCON WINDOW	
△ 4	GG30019-001B-H	POWER KNOB	
△ 5	CM30861-069	SPRING	
△ 6	GG20006-001A-H	CONTROL KNOB	
△ 7	GG30021-002A-H	LED LENS	
△ 8	A48457-1	SPRING	
△ 9	CHGB0016-0B-N	BRAIDED ASSY	
△ 10	QAS0086-001	SPEAKER	(X2)SP01
△ 11	CM36623-B01-H	CHASSIS RAIL	(X2)
△ 12	CM47005-A01-H	CORD CLAMP	
△ 13	QMP40D0-200J5	POWER CORD	or QMP40D0-200J3
△ 14	GG10130-005A-HK	REAR COVER	
△ 15	GG20016-019A-E	RATING LABEL	
△ 16	GG40015-001A-E	SERIAL LABEL	
△ 17	QYSBSF3010Z	TAP SCREW	(X1)
△ 18	QYSBSFG4016Z	TAP SCREW	(X7)

EXPLODED VIEW (1)



EXPLODED VIEW (2)



PRINTED WIRING BOARD PARTS LIST

[AV-21D73_{NT}]

MAIN P.W. BOARD ASS'Y (SCG-1438A)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R1002	NRSA02J-221X	MG R	220Ω 1/10W J
R1003	NRSA02J-221X	MG R	220Ω 1/10W J
R1004	NRSA02J-563X	MG R	56kΩ 1/10W J
R1102	NRSA02J-750X	MG R	75Ω 1/10W J
R1103	NRSA02J-820X	MG R	82Ω 1/10W J
R1109	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1110	NRSA02J-272X	MG R	2.7kΩ 1/10W J
R1111	NRSA02J-181X	MG R	180Ω 1/10W J
R1112	NRSA02J-220X	MG R	22Ω 1/10W J
R1113	NRSA02J-101X	MG R	100Ω 1/10W J
R1114	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1115	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1117	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1118	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1120	NRSA02J-391X	MG R	390Ω 1/10W J
R1121	NRSA02J-221X	MG R	220Ω 1/10W J
R1159	NRSA02J-184X	MG R	180kΩ 1/10W J
R1161	NRSA02J-102X	MG R	1kΩ 1/10W J
R1162	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1163	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1164	NRSA02J-221X	MG R	220Ω 1/10W J
R1165	NRSA02J-220X	MG R	22Ω 1/10W J
R1166	NRSA02J-821X	MG R	820Ω 1/10W J
R1301	NRSA02J-221X	MG R	220Ω 1/10W J
R1302	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1303	NRSA02J-221X	MG R	220Ω 1/10W J
R1304	NRSA02J-221X	MG R	220Ω 1/10W J
R1305	NRSA02J-221X	MG R	220Ω 1/10W J
R1306	NRSA02J-221X	MG R	220Ω 1/10W J
R1307	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1308	NRSA02J-182X	MG R	1.8kΩ 1/10W J
R1312	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1313	NRSA02J-102X	MG R	1kΩ 1/10W J
R1314	NRSA02J-102X	MG R	1kΩ 1/10W J
R1321	NRSA02J-152X	MG R	1.5kΩ 1/10W J
R1322	NRSA02J-272X	MG R	2.7kΩ 1/10W J
R1323	NRSA02J-103X	MG R	10kΩ 1/10W J
R1324	NRSA02J-102X	MG R	1kΩ 1/10W J
R1326	NRSA02J-101X	MG R	100Ω 1/10W J
R1327	NRSA02J-475X	MG R	4.7MΩ 1/10W J
R1341	NRSA02J-332X	MG R	3.3kΩ 1/10W J
R1345	NRSA02J-151X	MG R	150Ω 1/10W J
R1346	NRSA02J-151X	MG R	150Ω 1/10W J
R1347	NRSA02J-392X	MG R	3.9kΩ 1/10W J
R1348	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1353	NRSA02J-151X	MG R	150Ω 1/10W J
R1354	NRSA02J-331X	MG R	330Ω 1/10W J
R1355	NRSA02J-331X	MG R	330Ω 1/10W J
R1356	NRSA02J-331X	MG R	330Ω 1/10W J
R1357	NRSA02J-101X	MG R	100Ω 1/10W J
R1358	NRSA02J-101X	MG R	100Ω 1/10W J
R1359	NRSA02J-101X	MG R	100Ω 1/10W J
R1360	QRZ0107-152Z	C R	1.5kΩ 1/2W K
R1361	QRZ0107-152Z	C R	1.5kΩ 1/2W K
R1362	QRZ0107-152Z	C R	1.5kΩ 1/2W K
R1363	QRL029J-123	OM R	12kΩ 2W J
R1364	QRL029J-123	OM R	12kΩ 2W J
R1365	QRL029J-123	OM R	12kΩ 2W J
R1366	NRSA02J-182X	MG R	1.8kΩ 1/10W J
R1367	NRSA02J-182X	MG R	1.8kΩ 1/10W J
R1368	NRSA02J-182X	MG R	1.8kΩ 1/10W J
R1369	QRE122J-394	C R	390kΩ 1/2W J
R1372	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1374	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1401	NRSA02J-103X	MG R	10kΩ 1/10W J
R1421	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1422	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1423	NRSA02J-331X	MG R	330Ω 1/10W J
R1424	NRSA02J-101X	MG R	100Ω 1/10W J
R1425	NRSA02J-471X	MG R	470Ω 1/10W J
R1426	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1429	NRSA02J-103X	MG R	10kΩ 1/10W J
R1430	NRSA02J-823X	MG R	82kΩ 1/10W J

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R1431	NRSA02J-103X	MG R	10kΩ 1/10W J
R1432	QRE122J-2R7	C R	2.7Ω 1/2W J
R1433	QRE122J-2R7	C R	2.7Ω 1/2W J
R1436	NRSA02J-823X	MG R	82kΩ 1/10W J
R1440	QRE122J-471	C R	470Ω 1/2W J
R1441	NRSA02J-822X	MG R	8.2kΩ 1/10W J
R1442	NRSA02J-103X	MG R	10kΩ 1/10W J
R1443	QRE122J-1R0	C R	1.0Ω 1/2W J
R1453	NRSA02J-272X	MG R	2.7kΩ 1/10W J
R1501	QRE122J-101	C R	100Ω 1/2W J
R1502	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1503	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1521	NRSA02J-681X	MG R	680Ω 1/10W J
R1522	NRSA02J-103X	MG R	10kΩ 1/10W J
R1524	QRL02EJ-820X	OM R	82Ω 2W J
R1525	QRL02EJ-820X	OM R	82Ω 2W J
R1526	QRE121J-270Y	C R	27Ω 1/2W J
R1528	QRE122J-471	C R	470Ω 1/2W J
R1530	QRE122J-223	C R	22kΩ 1/2W J
R1531	NRSA02J-103X	MG R	10kΩ 1/10W J
R1532	NCB21HK-103X	C CAP.	0.01μF 50V K
R1533	NRSA02J-332X	MG R	3.3kΩ 1/10W J
R1534	NRSA02J-332X	MG R	3.3kΩ 1/10W J
△ R1551	QRZ9011-1R0	F R	1.0 Ω 1/2W J
△ R1552	QRJ146J-2R2X	C R	2.2Ω 1/4W J
R1554	QRE122J-821	C R	820Ω 1/2W J
R1571	QRE122J-222	C R	2.2kΩ 1/2W J
R1573	QRT02EJ-1R5X	MF R	1.5Ω 2W J
R1574	QRT02EJ-1R5X	MF R	1.5Ω 2W J
R1576	QRE122J-223	C R	22kΩ 1/2W J
R1577	NRSA02J-392X	MG R	3.9kΩ 1/10W J
R1578	NRSA02J-103X	MG R	10kΩ 1/10W J
R1581	QRE122J-182	C R	1.8kΩ 1/2W J
R1582	NRSA02J-223X	MG R	22kΩ 1/10W J
R1583	NRSA02J-393X	MG R	39kΩ 1/10W J
R1651	NRSA02J-103X	MG R	10kΩ 1/10W J
R1652	NRSA02J-102X	MG R	1kΩ 1/10W J
R1653	QRE122J-1R0	C R	1.0Ω 1/2W J
R1654	QRX029J-4R7	MF R	4.7Ω 2W J
R1656	NRSA02J-123X	MG R	12kΩ 1/10W J
R1657	NRSA02J-391X	MG R	390Ω 1/10W J
R1658	NRSA02J-102X	MG R	1kΩ 1/10W J
R1659	NRSA02J-102X	MG R	1kΩ 1/10W J
R1660	NRSA02J-103X	MG R	10kΩ 1/10W J
R1661	QRE122J-271	C R	270Ω 1/2W J
R1662	QRE122J-271	C R	270Ω 1/2W J
R1664	NRSA02J-221X	MG R	220Ω 1/10W J
R1665	NRSA02J-103X	MG R	10kΩ 1/10W J
R1701	NRSA02J-562X	MG R	5.6kΩ 1/10W J
R1702	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1703	NRSA02J-392X	MG R	3.9kΩ 1/10W J
R1704	NRSA02J-221X	MG R	220Ω 1/10W J
R1705	NRSA02J-221X	MG R	220Ω 1/10W J
R1706	NRSA02J-561X	MG R	560Ω 1/10W J
R1707	NRSA02J-561X	MG R	560Ω 1/10W J
R1708	NRSA02J-102X	MG R	1kΩ 1/10W J
R1709	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1710	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1711	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1712	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1713	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1714	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1715	NRSA02J-221X	MG R	220Ω 1/10W J
R1716	NRSA02J-221X	MG R	220Ω 1/10W J
R1718	NRSA02J-561X	MG R	560Ω 1/10W J
R1719	NRSA02J-102X	MG R	1kΩ 1/10W J
R1720	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1721	NRSA02J-103X	MG R	10kΩ 1/10W J
△ R1723	QRZ9023-270	F R	27 Ω 2W J
R1725	NRSA02J-102X	MG R	1kΩ 1/10W J
R1726	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1727	NRSA02J-153X	MG R	15kΩ 1/10W J
R1728	NRSA02J-102X	MG R	1kΩ 1/10W J

[AV-21D73_{MT}]

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R1729	NRSA02J-102X	MG R	1kΩ 1/10W J
R1730	NRSA02J-103X	MG R	10kΩ 1/10W J
R1731	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1736	NRSA02J-823X	MG R	82kΩ 1/10W J
R1737	NRSA02J-104X	MG R	100kΩ 1/10W J
R1738	NRSA02J-103X	MG R	10kΩ 1/10W J
R1739	NRSA02J-103X	MG R	10kΩ 1/10W J
R1740	NRSA02J-392X	MG R	3.9kΩ 1/10W J
R1741	NRSA02J-561X	MG R	560Ω 1/10W J
R1742	NRSA02J-563X	MG R	56kΩ 1/10W J
R1746	NRSA02J-103X	MG R	10kΩ 1/10W J
R1747	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1748	NRSA02J-223X	MG R	22kΩ 1/10W J
R1749	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1771	NRSA02J-821X	MG R	820Ω 1/10W J
R1772	NRSA02J-821X	MG R	820Ω 1/10W J
R1791	NRSA02J-221X	MG R	220Ω 1/10W J
R1792	NRSA02J-221X	MG R	220Ω 1/10W J
R1793	NRSA02J-221X	MG R	220Ω 1/10W J
R1794	NRSA02J-221X	MG R	220Ω 1/10W J
R1795	NRSA02J-221X	MG R	220Ω 1/10W J
R1796	NRSA02J-103X	MG R	10kΩ 1/10W J
R1797	NRSA02J-153X	MG R	15kΩ 1/10W J
R1802	NRSA02J-750X	MG R	75Ω 1/10W J
R1806	QRE122J-271	C R	270Ω 1/2W J
R1807	NRSA02J-680X	MG R	68Ω 1/10W J
R1810	QRG01GJ-560	OM R	56Ω 1W J
R1811	NRSA02J-221X	MG R	220Ω 1/10W J
R1815	QRE121J-181Y	C R	180Ω 1/2W J
R1816	NRSA02J-681X	MG R	680Ω 1/10W J
R1817	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1901	QRF104K-3R9	UNF R	3.9Ω 10W K
R1903	QRL02EJ-683X	OM R	68kΩ 2W J
R1921	QRE122J-681	C R	680Ω 1/2W J
R1922	QRT029J-1R2	MF R	1.2Ω 2W J
R1923	QRM059J-R22	MP R	0.22Ω 5W J
R1926	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1928	QRL03EJ-563X	OM R	56kΩ 3W J
R1929	QRE121J-822Y	C R	8.2kΩ 1/2W J
△ R1932	QRE122J-564	C R	560kΩ 1/2W J
R1933	QRE122J-220	C R	22Ω 1/2W J
R1934	NRSA02J-333X	MG R	33kΩ 1/10W J
R1936	QRG01GJ-561	OM R	560Ω 1W J
R1941	QRE122J-821	C R	820Ω 1/2W J
R1942	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1943	NRSA02J-473X	MG R	47kΩ 1/10W J
R1944	NRSA02J-103X	MG R	10kΩ 1/10W J
R1974	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1976	NRSA02J-102X	MG R	1kΩ 1/10W J
R1977	QRE122J-122	C R	1.2kΩ 1/2W J
R1978	NRSA02J-473X	MG R	47kΩ 1/10W J
R1979	QRT02EJ-1R2X	MF R	1.2Ω 2W J
R1980	QRL02EJ-103X	OM R	10kΩ 2W J
△ R1991	QRZ0057-825	C R	8.2MΩ 1W J

CAPACITOR

C1001	QETM1HM-106	E CAP.	10μF 50V M
C1002	NCB21HK-103X	C CAP.	0.01μF 50V K
C1004	QETM1CM-477	E CAP.	470μF 16V M
C1005	QFV81HJ-104	MF CAP.	0.1μF 50V J
C1008	QETM1HM-475	E CAP.	4.7μF 50V M
C1103	QETM1EM-476	E CAP.	47μF 25V M
C1104	NCB21HK-472X	C CAP.	4700pF 50V K
C1105	NCB21HK-472X	C CAP.	4700pF 50V K
C1106	NCB21HK-472X	C CAP.	4700pF 50V K
C1107	NCB21HK-472X	C CAP.	4700pF 50V K
C1109	NCB21HK-472X	C CAP.	4700pF 50V K
C1110	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
C1112	QETM1EM-476	E CAP.	47μF 25V M
C1113	NCB21HK-472X	C CAP.	4700pF 50V K
C1115	NCB21HK-103X	C CAP.	0.01μF 50V K
C1116	NCB21HK-103X	C CAP.	0.01μF 50V K
C1117	QFV81HJ-224	MF CAP.	0.22μF 50V J
C1119	QETM1HM-474	E CAP.	0.47μF 50V M
C1120	NDC21HJ-121X	C CAP.	120pF 50V J
C1121	NCB21HK-103X	C CAP.	0.01μF 50V K

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			

C1122	NCB21HK-103X	C CAP.	0.01μF 50V K
C1161	NCB21HK-103X	C CAP.	0.01μF 50V K
C1162	NCB21HK-152X	C CAP.	1500pF 50V K
C1164	NCB21HK-103X	C CAP.	0.01μF 50V K
C1165	NCB21HK-103X	C CAP.	0.01μF 50V K
C1166	NCB21HK-104X	C CAP.	0.1μF 50V K
C1301	NCB21HK-123X	C CAP.	0.012μF 50V K
C1302	QETM1HM-475	E CAP.	4.7μF 50V M
C1303	NDC21HJ-100X	C CAP.	10pF 50V J
C1304	QFV81HJ-474	MF CAP.	0.47μF 50V J
C1305	QETM1HM-474	E CAP.	0.47μF 50V M
C1306	NCB21HK-103X	C CAP.	0.01μF 50V K
C1307	QETM1CM-477	E CAP.	470μF 16V M
C1308	QETM1CM-107	E CAP.	100μF 16V M
C1309	NCB21HK-103X	C CAP.	0.01μF 50V K
C1310	NDC21HJ-221X	C CAP.	220pF 50V J
C1311	NCB21HK-103X	C CAP.	0.01μF 50V K
C1312	QENC1HM-474Z	E CAP.	0.47μF 50V M
C1313	QETM1HM-335Z	E CAP.	3.3μF 50V M
C1314	NCB21HK-103X	C CAP.	0.01μF 50V K
C1315	QETM1CM-107	E CAP.	100μF 16V M
C1316	QETM1HM-106	E CAP.	10μF 50V M
C1317	NCB21HK-473X	C CAP.	0.047μF 50V K
C1321	NDC21HJ-120X	C CAP.	12pF 50V J
C1322	NCB21HK-273X	C CAP.	0.027μF 50V K
C1323	QETM1HM-474	E CAP.	0.47μF 50V M
C1324	QETM1HM-106	E CAP.	10μF 50V M
C1325	QENB1HM-106	E CAP.	10μF 50V M
C1326	NCS21HJ-221X	C CAP.	220pF 50V J
C1341	QETM1HM-106	E CAP.	10μF 50V M
C1352	QFZ0097-103	MM CAP.	0.01μF 1250V K
C1354	NDC21HJ-221X	C CAP.	220pF 50V J
C1355	NDC21HJ-271X	C CAP.	270pF 50V J
C1356	NDC21HJ-331X	C CAP.	330pF 50V J
C1357	QETM1AM-477Z	E CAP.	470μF 10V M
C1365	QENB1HM-105	E CAP.	1μF 50V M
C1366	QENB1HM-105	E CAP.	1μF 50V M
C1367	QENB1HM-105	E CAP.	1μF 50V M
C1401	QFV81HJ-474	MF CAP.	0.47μF 50V J
C1402	QFV71HJ-104Z	MF CAP.	0.1μF 50V J
C1422	QETM1HM-105	E CAP.	1μF 50V M
C1423	QCS32HJ-180Z	C CAP.	18pF 500V J
C1424	QFLB2AJ-103	M CAP.	0.01μF 100V J
C1426	QFLB1HJ-102	M CAP.	1000pF 50V J
C1427	QETM1VM-107	E CAP.	100μF 35V M
C1428	QEHQ1VM-107	E CAP.	100μF 35V M
C1429	QETM1HM-106	E CAP.	10μF 50V M
C1430	QFLC2AJ-472Z	M CAP.	4700pF 100V J
C1433	QEHQ1HM-475	E CAP.	4.7μF 50V M
C1435	QETM1EM-228	E CAP.	2200μF 25V M
C1436	QFV81HJ-334	MF CAP.	0.33μF 50V J
C1501	QETM1HM-476	E CAP.	47μF 50V M
C1502	NCB21HK-103X	C CAP.	0.01μF 50V K
C1503	QETM1HM-106	E CAP.	10μF 50V M
C1504	QETM1CM-227	E CAP.	220μF 16V M
C1523	QTMN1VM-476Z	E CAP.	47μF 35V M
△ C1525	QFZ0200-902	MPP CAP.	9000pF1.5kVH±3%
C1526	QTMN1EM-337Z	E CAP.	330μF 25V M
△ C1527	QFZ0199-304	MPP CAP.	0.3μF 250V J
C1528	QETM2EM-475	E CAP.	4.7μF 250V M
C1530	QCB32HK-561	C CAP.	560pF 500V K
C1531	QEZ0203-107	E CAP.	100μF 160V M
C1552	QETM1VM-108	E CAP.	1000μF 35V M
C1554	QETM2EM-475	E CAP.	4.7μF 250V M
C1555	QFLC2AJ-104Z	M CAP.	0.1μF 100V J
C1571	QETM1AM-107	E CAP.	100μF 10V M
C1572	QETM1EM-476	E CAP.	47μF 25V M
C1581	QFV81HJ-104	MF CAP.	0.1μF 50V J
△ C1582	QFZ0199-254	MPP CAP.	0.25μF 250V J
C1651	QTN1HM-105Z	E CAP.	1μF 50V M
C1652	QEHQ1HM-106	E CAP.	10μF 50V M
C1653	QEHQ1HM-106	E CAP.	10μF 50V M
C1654	NCB21HK-104X	C CAP.	0.1μF 50V K
C1655	QEHQ1VM-228	E CAP.	2200μF 35V M
C1656	QEHQ1EM-477	E CAP.	470μF 25V M
C1658	QETM1HM-226	E CAP.	22μF 50V M
C1659	QETM1CM-107	E CAP.	100μF 16V M
C1663	QEHQ1HM-106	E CAP.	10μF 50V M

[AV-21D73NT]

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C1664	NCB21HK-104X	C CAP.	0.1μF 50V K
C1665	QEH1HM-105Z	E CAP.	1μF 50V M
C1701	QETM1CM-106	E CAP.	10μF 50V M
C1705	QETM1CM-477	E CAP.	470μF 16V M
C1706	NCB21EK-104X	C CAP.	0.1μF 25V K
C1707	NCB21HK-103X	C CAP.	0.01μF 50V K
C1708	QETM1EM-476	E CAP.	47μF 25V M
C1709	NCB21HK-103X	C CAP.	0.01μF 50V K
C1710	QETM1CM-107	E CAP.	100μF 16V M
C1711	NCB21HK-103X	C CAP.	0.01μF 50V K
C1712	NCB21HK-103X	C CAP.	0.01μF 50V K
C1713	NCB21HK-103X	C CAP.	0.01μF 50V K
C1714	NDC21HJ-330X	C CAP.	33pF 50V J
C1715	NDC21HJ-330X	C CAP.	33pF 50V J
C1716	NDC21HJ-181X	C CAP.	180pF 50V J
C1717	NDC21HJ-181X	C CAP.	180pF 50V J
C1718	NCB21HK-103X	C CAP.	0.01μF 50V K
C1719	QETM1HM-105	E CAP.	1μF 50V M
C1720	NCB21HK-103X	C CAP.	0.01μF 50V K
C1721	NCB21HK-333X	C CAP.	0.033μF 50V K
C1722	NDC21HJ-101X	C CAP.	100pF 50V J
C1724	NDC21HJ-560X	C CAP.	56pF 50V J
C1728	NDC21HJ-181X	C CAP.	180pF 50V J
C1729	NDC21HJ-181X	C CAP.	180pF 50V J
C1730	NCB21HK-103X	C CAP.	0.01μF 50V K
C1738	QETM1HM-226	E CAP.	22μF 50V M
C1744	NCB21HK-103X	C CAP.	0.01μF 50V K
C1805	QETM1CM-227	E CAP.	220μF 16V M
C1806	QETM1CM-477	E CAP.	470μF 16V M
C1811	QETM1HM-106	E CAP.	10μF 50V M
C1841	NCB21HK-152X	C CAP.	1500pF 50V K
△ C1901	QFZ9040-104	MF CAP.	0.1μFAC275V M
△ C1904	QCZ9078-222	C CAP.	2200pFAC250V M
△ C1905	QCZ9078-222	C CAP.	2200pFAC250V M
△ C1907	QCZ9078-222	C CAP.	2200pFAC250V M
△ C1909	QEZO199-127	E CAP.	120μF 400V M
△ C1910	QFZ9040-473	MF CAP.	0.047μFAC275V M
C1922	QFLB1HJ-471	M CAP.	470pF 50V J
C1924	QETM1VM-107	E CAP.	100μF 35V M
C1926	QFLC1HJ-332Z	M CAP.	3300pF 50V J
C1928	NCB21HK-473X	C CAP.	0.047μF 50V K
C1929	QFP32GJ-223Z	PP CAP.	0.022μF 400V J
C1930	QCZ0325-561	C CAP.	560pF 2kV K
C1931	QCZ0325-151	C CAP.	150pF 2kV K
C1932	QCZ0325-151	C CAP.	150pF 2kV K
C1941	QCZ0122-561	C CAP.	560pF 2kV K
C1942	QEZO420-107	E CAP.	100μF 160V M
C1945	QEHQ1CM-108	E CAP.	1000μF 16V M
C1946	QEH1CM-477Z	E CAP.	470μF 16V M
C1948	QEHQ1VM-108	E CAP.	1000μF 35V M
C1949	NDC21HJ-471X	C CAP.	470pF 50V J
C1950	NCB21HK-104X	C CAP.	0.1μF 50V K
C1971	QETM1HM-226	E CAP.	22μF 50V M
C1976	QETM1HM-105	E CAP.	1μF 50V M
C1977	QETM1CM-477	E CAP.	470μF 16V M
C1978	QETM1CM-227	E CAP.	220μF 16V M
C1979	QETM1CM-107	E CAP.	100μF 16V M
△ C1991	QCZ9079-471	C CAP.	470pFAC250V K
△ C1992	QCZ9079-471	C CAP.	470pFAC250V K
△ C1993	QCZ9079-102	C CAP.	1000pFAC250V M

TRANSFORMER

△ T1522	QQH0070-001-KD	FBT	
△ T1921	QQS0050-001	SW TRANSF.	or QQS0056-001

COIL

L1001	QQL242K-8R2	COIL	8.2μH K
L1101	QQL2014-2R2	INDUCTOR	
L1103	QQL242K-8R2	COIL	8.2μH K
L1522	CE41210-00B	LIN COIL	
L1523	QQL342J-2R2Z	INDUCTOR	
L1551	QQL2018-860	INDUCTOR	
L1701	QQL244J-5R6Z	COIL	5.6μH J
L1941	QQL26AK-820Z	COIL	82μH K
L1942	QQL26AK-820Z	COIL	82μH K
L1943	QQL26AK-820Z	COIL	82μH K

△ Symbol No.	Part No.	Part Name	Description
DIODE			
D1001	MA3330/L/-X	ZENER DIODE	
D1102	MA859-T2	SI DIODE	
D1301	MA3091/M/-X	ZENER DIODE	
D1302	MA3091/M/-X	ZENER DIODE	
D1305	RB100A-T2	SB DIODE	
D1306	1SR124-400A-T2	SI DIODE	
D1341	MA111-X	SI DIODE	
D1342	MA111-X	SI DIODE	
D1421	MA3360/M/-X	ZENER DIODE	
D1422	MA3360/M/-X	ZENER DIODE	
D1423	1SR124-400A-T2	SI DIODE	
D1424	MA111-X	SI DIODE	
D1425	MA111-X	SI DIODE	
D1427	MA3270/H/-X	ZENER DIODE	
D1551	RGP10J-TS-T3	SI DIODE	
D1552	RH15-T3	SI DIODE	
D1553	MA3091/M/-X	ZENER DIODE	
D1554	MA111-X	SI DIODE	
D1555	1SR124-400A-T2	SI DIODE	
D1571	MA3075/M/-X	ZENER DIODE	
D1581	MA3200/M/-X	ZENER DIODE	
D1582	RGP10J-TS-T3	SI DIODE	
D1651	MA111-X	SI DIODE	
D1652	MA111-X	SI DIODE	
D1653	MTZJ18A-T2	ZENER DIODE	
D1701	MA111-X	SI DIODE	
D1704	L-132XID-T16	LED	
D1705	L-132XND-T16	LED	
D1706	MA111-X	SI DIODE	
D1707	MA111-X	SI DIODE	
D1731	MA111-X	SI DIODE	
△ D1901	G2SBA60	BRIDGE DIODE	
D1921	RGP10J-TS-T3	SI DIODE	
D1922	MA111-X	SI DIODE	
D1923	MA111-X	SI DIODE	
D1924	MA111-X	SI DIODE	
D1926	MA3056/M/-X	ZENER DIODE	
D1927	MA3068/M/-X	ZENER DIODE	
D1929	RD12E/B2/-T5	ZENER DIODE	
D1930	EG1A-T3	SI DIODE	
D1932	MA111-X	SI DIODE	
D1933	RD27E/B2/-T5	ZENER DIODE	
D1941	RU3AM-LFC4	SI DIODE	
D1942	RU3YX-LFC4	SI DIODE	
D1943	RGP10J-TS-T3	SI DIODE	
△ D1945	MA3075/H/-X	ZENER DIODE	
D1982	MA111-X	SI DIODE	
D1983	MA111-X	SI DIODE	

TRANSISTOR

Q1102	2SC5083/L-P/-T	SI TRANSISTOR	
Q1103	UN2212-X	DIGI. TRANSISTOR	
Q1161	2SD601A/QR/-X	SI TRANSISTOR	
Q1301	2SB709A/QR/-X	SI TRANSISTOR	
Q1302	2SD601A/QR/-X	SI TRANSISTOR	
Q1351	2SC3271F	SI TRANSISTOR	
Q1352	2SC3271F	SI TRANSISTOR	
Q1353	2SC3271F	SI TRANSISTOR	
Q1401	DTC124ESA-T	DIGI. TRANSISTOR	
Q1402	2SD601A/QR/-X	SI TRANSISTOR	
Q1521	2SK3065-W	MOS FET	
△ Q1522	2SC5388-CA	POWER TRANSISTOR	H. OUT
Q1523	2SD601A/QR/-X	SI TRANSISTOR	
Q1524	2SD601A/QR/-X	SI TRANSISTOR	
Q1571	2SA1208/ST/Z1-T	SI TRANSISTOR	
Q1572	2SD601A/QR/-X	SI TRANSISTOR	
Q1651	2SB709A/QR/-X	SI TRANSISTOR	
Q1652	DTC323TK-X	DIGI. TRANSISTOR	
Q1654	2SD601A/QR/-X	SI TRANSISTOR	
Q1655	2SD601A/QR/-X	SI TRANSISTOR	
Q1702	2SD601A/QR/-X	SI TRANSISTOR	
Q1703	2SD601A/QR/-X	SI TRANSISTOR	
Q1708	UN2212-X	DIGI. TRANSISTOR	
Q1709	2SB709A/QR/-X	SI TRANSISTOR	
Q1803	2SC1815/YG/-T	SI TRANSISTOR	
Q1804	2SD601A/QR/-X	SI TRANSISTOR	
Q1941	2SD601A/QR/-X	SI TRANSISTOR	
Q1943	UN2211-X	DIGI. TRANSISTOR	
Q1974	2SA966/QY/-T	SI TRANSISTOR	
Q1975	UN2212-X	DIGI. TRANSISTOR	

[AV-21D73_{VT}]



△ Symbol No.	Part No.	Part Name	Description
I C			
	IC1301	NN5198K	I C
	IC1421	AN5539-LF	I C
	IC1651	LA4287	I C
	IC1652	SI-5003X-X	I C
△	IC1701	MN1873287JM	I C
	IC1702	AT24C08-21D73VT	I C (SERVICE)
	IC1703	L78LR05E-MA	I C
	IC1704	PIC-28143SY	IR DETECT UNIT or G01U281Q or PIC-47143SY
△	IC1921	STR-G6653	I C
	IC1941	SE115N-LF12	I C
	IC1971	BA51W12ST-V5	I C
OTHERS			
		LC30114-001C-H	LED HOLDER
		CM35921-B02	CDS HOLDER
△	CF1161	QAX0642-001Z	C FILTER
△	CP1981	ICP-N75	C PROTECTOR
△	CP1982	ICP-N75	C PROTECTOR
△	F1901	QMF51E2-3R15J4	FUSE 3.15A
	FC1901	CEMG002-001Z	FUSE CLIP
	J1002	CEMN075-001	PIN JACK
	J1003	QNN0281-003	PIN JACK or CEMN065-001
	J1004	QNN0281-002	PIN JACK or CEMN065-002
△	J1005	QNS0165-001	3.5 JACK
	J1006	QNN0281-002	PIN JACK or CEMN065-002
	K1001	QQR0621-002Z	FERRITE BEADS
	K1351	QQR0621-002Z	FERRITE BEADS
	K1421	QQR0582-001Z	FERRITE BEADS
	K1921	QQR1113-001Z	FERRITE BEADS
	K1922	QQR1113-001Z	FERRITE BEADS
	K1923	QQR1114-001Z	FERRITE BEADS
	K1924	QQR1113-001Z	FERRITE BEADS
	K1941	QQR1113-001Z	FERRITE BEADS
	K1942	QQR1113-001Z	FERRITE BEADS
	K1943	QQR1113-001Z	FERRITE BEADS
△	LF1901	QQR0527-002	LINE FILTER
	PC1701	P1241-04	PHOTO CONDUCTOR
△	PC1921	PC123F2	IC(PHOTO COUPLE or TLP721F(D4-GR)
	S1701	QSW0619-003Z	TACT SWITCH MENU
	S1702	QSW0619-003Z	TACT SWITCH CH-
	S1703	QSW0619-003Z	TACT SWITCH CH+
	S1704	QSW0619-003Z	TACT SWITCH VOL-
	S1705	QSW0619-003Z	TACT SWITCH VOL+
△	S1901	QSW0750-001	PUSH SWITCH POWER SW
	SF1102	QAX0594-001	SAW FILTER
	SF1122	QAX0325-001	SAW FILTER
△	SK1351	CE42554-001	C R T SOCKET
△	TH1901	QAD0119-9R0	THERMISTOR or QAD0121-9R0
△	TU1001	QAU0186-002	TUNER
△	VA1901	ERZV10V621CS	VARISTOR or QAF0052-621
	X1301	QAX0500-001Z	CRYSTAL
	X1302	CE42690-001Z	CRYSTAL
	X1701	FCR12.0M2S	CRYSTAL

PACKING PARTS LIST

[AV-21D73/VT]

△ Ref.No.	Part No.	Part Name	Description
1	GG10007-023A-E	PACKING CASE	4pcs in 1set or CP30967-005-H
2	GG10131-003A-E	CUSHION ASSY	
3	GG30033-001A-E	POLY BAG	
4	RM-C367GY-1H	REMOCON UNIT	
5	GG40015-001A-E	SERIAL LABEL	
6	GG30034-001A-E	POLY BAG	
△ 7	LCT1210-001A	INST BOOK	
8	CEAB005-00AJ1	MATCHING BOX	
9	CM35847-00B-H	ROD ANTENNA	

PACKING




AV-16N73_{VT}


EXPLODED VIEW PARTS LIST

△ Ref.No.	Part No.	Part Name	Description
△ V01	A38JLL91X13	ITC	
△ L01	QQW0103-001	DEG COIL	or QQW0022-001
△ T1522	QQH0072-001-KD	FBT	
△ 1	LC10617-008A-E	FRONT CABINET	
△ 2	LC40606-003A	JVC MARK	
△ 3	LC30617-001C-H	E.E.WINDOW	
△ 4	LC30616-004A-H	POWER KNOB	
△ 5	CM30861-084	SPRING	
△ 6	LC20292-004A-H	CONTROL KNOB	
△ 7	LC30618-001B-H	LED LENS	
△ 8	A48457-1	SPRING	
△ 9	WJY0008-001A	E-BRAIDED ASSY	
△ 10	CEB5S09D-05KJ2	SPEAKER	(X2)SP01,SP02
△ 11	CM36623-B01-H	CHASSIS RAIL	(X2)
△ 12	CM48144-002-H	PB STOPPER	
△ 13	CM47005-A01-H	CORD CLAMP	
△ 14	QMP40D0-200J5	POWER CORD	or QMP40D0-200J3
△ 15	LC10618-001A	REAR COVER	
△ 16	GG20016-018A-E	RATING LABEL	
△ 17	GG40015-001A-E	SERIAL LABEL	
△ 18	GG30003-001A-H	TERMINAL SHEET	
△ 19	QYSBSF3010Z	TAP SCREW	(X1)
△ 20	QYSBSFG4016Z	TAP SCREW	(X5)

EXPLODED VIEW (1)



EXPLODED VIEW (2)



PRINTED WIRING BOARD PARTS LIST

[AV-16N73/NT]

MAIN P.W. BOARD ASS'Y (SCG-1437A)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R1002	NRSA02J-221X	MG R	220Ω 1/10W J
R1003	NRSA02J-221X	MG R	220Ω 1/10W J
R1004	NRSA02J-563X	MG R	56kΩ 1/10W J
R1102	NRSA02J-750X	MG R	75Ω 1/10W J
R1103	NRSA02J-820X	MG R	82Ω 1/10W J
R1109	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1110	NRSA02J-272X	MG R	2.7kΩ 1/10W J
R1111	NRSA02J-181X	MG R	180Ω 1/10W J
R1112	NRSA02J-220X	MG R	22Ω 1/10W J
R1113	NRSA02J-101X	MG R	100Ω 1/10W J
R1114	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1115	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1117	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1118	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1120	NRSA02J-391X	MG R	390Ω 1/10W J
R1121	NRSA02J-221X	MG R	220Ω 1/10W J
R1159	NRSA02J-184X	MG R	180kΩ 1/10W J
R1161	NRSA02J-102X	MG R	1kΩ 1/10W J
R1162	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1163	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1164	NRSA02J-221X	MG R	220Ω 1/10W J
R1165	NRSA02J-220X	MG R	22Ω 1/10W J
R1166	NRSA02J-821X	MG R	820Ω 1/10W J
R1301	NRSA02J-221X	MG R	220Ω 1/10W J
R1302	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1303	QRE141J-101Y	C R	100Ω 1/4W J
R1304	NRSA02J-101X	MG R	100Ω 1/10W J
R1305	NRSA02J-101X	MG R	100Ω 1/10W J
R1306	NRSA02J-221X	MG R	220Ω 1/10W J
R1307	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1308	NRSA02J-182X	MG R	1.8kΩ 1/10W J
R1312	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1313	NRSA02J-102X	MG R	1kΩ 1/10W J
R1314	NRSA02J-102X	MG R	1kΩ 1/10W J
R1321	NRSA02J-152X	MG R	1.5kΩ 1/10W J
R1322	NRSA02J-272X	MG R	2.7kΩ 1/10W J
R1323	NRSA02J-103X	MG R	10kΩ 1/10W J
R1324	NRSA02J-102X	MG R	1kΩ 1/10W J
R1326	NRSA02J-101X	MG R	100Ω 1/10W J
R1327	NRSA02J-475X	MG R	4.7MΩ 1/10W J
R1341	NRSA02J-332X	MG R	3.3kΩ 1/10W J
R1345	NRSA02J-151X	MG R	150Ω 1/10W J
R1346	NRSA02J-151X	MG R	150Ω 1/10W J
R1347	NRSA02J-392X	MG R	3.9kΩ 1/10W J
R1348	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1353	NRSA02J-151X	MG R	150Ω 1/10W J
R1354	NRSA02J-331X	MG R	330Ω 1/10W J
R1355	NRSA02J-331X	MG R	330Ω 1/10W J
R1356	NRSA02J-331X	MG R	330Ω 1/10W J
R1357	NRSA02J-101X	MG R	100Ω 1/10W J
R1358	NRSA02J-101X	MG R	100Ω 1/10W J
R1359	NRSA02J-101X	MG R	100Ω 1/10W J
R1360	QRZ0107-152Z	C R	1.5kΩ 1/2W K
R1361	QRZ0107-152Z	C R	1.5kΩ 1/2W K
R1362	QRZ0107-152Z	C R	1.5kΩ 1/2W K
R1363	QRL029J-123	OM R	12kΩ 2W J
R1364	QRL029J-123	OM R	12kΩ 2W J
R1365	QRL029J-123	OM R	12kΩ 2W J
R1366	NRSA02J-182X	MG R	1.8kΩ 1/10W J
R1367	NRSA02J-182X	MG R	1.8kΩ 1/10W J
R1368	NRSA02J-182X	MG R	1.8kΩ 1/10W J
R1369	QRE122J-394	C R	390kΩ 1/2W J
R1372	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1374	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1401	NRSA02J-103X	MG R	10kΩ 1/10W J
R1421	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1422	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1423	NRSA02J-331X	MG R	330Ω 1/10W J
R1424	NRSA02J-101X	MG R	100Ω 1/10W J
R1425	NRSA02J-471X	MG R	470Ω 1/10W J
R1426	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1429	NRSA02J-103X	MG R	10kΩ 1/10W J
R1430	NRSA02J-823X	MG R	82kΩ 1/10W J

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R1431	NRSA02J-103X	MG R	10kΩ 1/10W J
R1432	QRE122J-3R9	C R	3.9Ω 1/2W J
R1433	QRE122J-3R9	C R	3.9Ω 1/2W J
R1434	QRE122J-821	C R	820Ω 1/2W J
R1436	NRSA02J-823X	MG R	82kΩ 1/10W J
R1440	QRE122J-561	C R	560Ω 1/2W J
R1441	NRSA02J-822X	MG R	8.2kΩ 1/10W J
R1442	NRSA02J-103X	MG R	10kΩ 1/10W J
R1443	QRE122J-1R0	C R	1.0Ω 1/2W J
R1453	NRSA02J-272X	MG R	2.7kΩ 1/10W J
R1501	QRE122J-101	C R	100Ω 1/2W J
R1502	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1503	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1521	NRSA02J-681X	MG R	680Ω 1/10W J
R1522	NRSA02J-103X	MG R	10kΩ 1/10W J
R1524	QRL03EJ-680X	OM R	68Ω 3W J
R1526	QRE121J-270Y	C R	27Ω 1/2W J
R1528	QRE122J-471	C R	470Ω 1/2W J
R1529	QRG029J-221	OMF R	220Ω 2W J
R1531	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1532	NCB21HK-103X	C CAP.	0.01μF 50V K
R1533	NRSA02J-332X	MG R	3.3kΩ 1/10W J
R1534	NRSA02J-332X	MG R	3.3kΩ 1/10W J
△ R1551	QRZ9011-1R0	F R	1.0Ω 1/2W J
△ R1552	QRJ146J-2R2X	C R	2.2Ω 1/4W J
R1554	QRE122J-182	C R	1.8kΩ 1/2W J
R1571	QRE122J-272	C R	2.7kΩ 1/2W J
R1573	QRT02EJ-1R5X	MF R	1.5Ω 2W J
R1574	QRT02EJ-2R7X	MF R	2.7Ω 2W J
R1576	QRE122J-223	C R	22kΩ 1/2W J
R1577	NRSA02J-562X	MG R	5.6kΩ 1/10W J
R1578	NRSA02J-103X	MG R	10kΩ 1/10W J
R1581	QRE122J-182	C R	1.8kΩ 1/2W J
R1582	NRSA02J-273X	MG R	27kΩ 1/10W J
R1583	NRSA02J-393X	MG R	39kΩ 1/10W J
R1651	NRSA02J-103X	MG R	10kΩ 1/10W J
R1652	NRSA02J-102X	MG R	1kΩ 1/10W J
R1653	QRE122J-1R0	C R	1.0Ω 1/2W J
R1654	QRX029J-4R7	MF R	4.7Ω 2W J
R1656	NRSA02J-123X	MG R	12kΩ 1/10W J
R1657	NRSA02J-391X	MG R	390Ω 1/10W J
R1658	NRSA02J-102X	MG R	1kΩ 1/10W J
R1659	NRSA02J-102X	MG R	1kΩ 1/10W J
R1660	NRSA02J-103X	MG R	10kΩ 1/10W J
R1661	QRE122J-271	C R	270Ω 1/2W J
R1662	QRE122J-271	C R	270Ω 1/2W J
R1664	NRSA02J-221X	MG R	220Ω 1/10W J
R1665	NRSA02J-103X	MG R	10kΩ 1/10W J
R1701	NRSA02J-562X	MG R	5.6kΩ 1/10W J
R1702	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1703	NRSA02J-392X	MG R	3.9kΩ 1/10W J
R1704	NRSA02J-221X	MG R	220Ω 1/10W J
R1705	NRSA02J-221X	MG R	220Ω 1/10W J
R1706	NRSA02J-561X	MG R	560Ω 1/10W J
R1707	NRSA02J-561X	MG R	560Ω 1/10W J
R1708	NRSA02J-102X	MG R	1kΩ 1/10W J
R1709	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1710	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1711	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1712	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1713	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1714	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1715	NRSA02J-221X	MG R	220Ω 1/10W J
R1716	NRSA02J-221X	MG R	220Ω 1/10W J
R1718	NRSA02J-561X	MG R	560Ω 1/10W J
R1719	NRSA02J-102X	MG R	1kΩ 1/10W J
R1720	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1721	NRSA02J-103X	MG R	10kΩ 1/10W J
△ R1723	QRZ9023-270	F R	27 Ω 2W J
R1725	NRSA02J-102X	MG R	1kΩ 1/10W J
R1726	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1727	NRSA02J-153X	MG R	15kΩ 1/10W J
R1728	NRSA02J-102X	MG R	1kΩ 1/10W J

[AV-16N73_{VT}]

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R1729	NRSA02J-102X	MG R	1kΩ 1/10W J
R1730	NRSA02J-103X	MG R	10kΩ 1/10W J
R1731	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1736	NRSA02J-823X	MG R	82kΩ 1/10W J
R1737	NRSA02J-104X	MG R	100kΩ 1/10W J
R1738	NRSA02J-103X	MG R	10kΩ 1/10W J
R1739	NRSA02J-103X	MG R	10kΩ 1/10W J
R1740	NRSA02J-392X	MG R	3.9kΩ 1/10W J
R1741	NRSA02J-561X	MG R	560Ω 1/10W J
R1742	NRSA02J-563X	MG R	56kΩ 1/10W J
R1746	NRSA02J-103X	MG R	10kΩ 1/10W J
R1747	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
R1748	NRSA02J-223X	MG R	22kΩ 1/10W J
R1749	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1771	NRSA02J-821X	MG R	820Ω 1/10W J
R1772	NRSA02J-821X	MG R	820Ω 1/10W J
R1791	NRSA02J-221X	MG R	220Ω 1/10W J
R1792	NRSA02J-221X	MG R	220Ω 1/10W J
R1793	NRSA02J-221X	MG R	220Ω 1/10W J
R1794	NRSA02J-221X	MG R	220Ω 1/10W J
R1795	NRSA02J-221X	MG R	220Ω 1/10W J
R1796	NRSA02J-103X	MG R	10kΩ 1/10W J
R1797	NRSA02J-153X	MG R	15kΩ 1/10W J
R1802	NRSA02J-750X	MG R	75Ω 1/10W J
R1806	QRE122J-271	C R	270Ω 1/2W J
R1807	NRSA02J-680X	MG R	68Ω 1/10W J
R1810	QRG01GJ-560	OM R	56Ω 1W J
R1811	NRSA02J-221X	MG R	220Ω 1/10W J
R1815	QRE121J-181Y	C R	180Ω 1/2W J
R1816	NRSA02J-681X	MG R	680Ω 1/10W J
R1817	NRSA02J-472X	MG R	4.7kΩ 1/10W J
R1901	QRFO74K-4R7	UNF R	4.7Ω 7W K
R1903	QRL02EJ-683X	OM R	68kΩ 2W J
R1921	QRE122J-681	C R	680Ω 1/2W J
R1922	QRT029J-1R2	MF R	1.2Ω 2W J
R1923	QRMO59J-R22	MP R	0.22Ω 5W J
R1926	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1928	QRL03EJ-563X	OM R	56kΩ 3W J
R1929	QRE121J-822Y	C R	8.2kΩ 1/2W J
△ R1932	QRE122J-564	C R	560kΩ 1/2W J
R1933	QRE121J-220Y	C R	22Ω 1/2W J
R1934	NRSA02J-333X	MG R	33kΩ 1/10W J
R1936	QRG01GJ-561	OM R	560Ω 1W J
R1941	QRE122J-821	C R	820Ω 1/2W J
R1942	NRSA02J-122X	MG R	1.2kΩ 1/10W J
R1943	NRSA02J-473X	MG R	47kΩ 1/10W J
R1944	NRSA02J-103X	MG R	10kΩ 1/10W J
R1974	NRSA02J-222X	MG R	2.2kΩ 1/10W J
R1976	NRSA02J-102X	MG R	1kΩ 1/10W J
R1977	QRE122J-122	C R	1.2kΩ 1/2W J
R1978	NRSA02J-473X	MG R	47kΩ 1/10W J
R1979	QRT02EJ-1R2X	MF R	1.2Ω 2W J
R1980	QRL02EJ-103X	OM R	10kΩ 2W J
R1985	QRE121J-120Y	C R	12Ω 1/2W J
R1986	NRSA02J-682X	MG R	6.8kΩ 1/10W J
R1987	NRSA02J-473X	MG R	47kΩ 1/10W J
R1988	NRSA02J-182X	MG R	1.8kΩ 1/10W J
△ R1991	QRZ0057-825	C R	8.2MΩ 1W J

CAPACITOR

C1001	QETM1HM-106	E CAP.	10μF 50V M
C1002	NCB21HK-103X	C CAP.	0.01μF 50V K
C1004	QETM1CM-227	E CAP.	220μF 16V M
C1005	QFV81HJ-104	MF CAP.	0.1μF 50V J
C1008	QETM1HM-475	E CAP.	4.7μF 50V M
C1103	QETM1EM-476	E CAP.	47μF 25V M
C1104	NCB21HK-472X	C CAP.	4700pF 50V K
C1105	NCB21HK-472X	C CAP.	4700pF 50V K
C1106	NCB21HK-472X	C CAP.	4700pF 50V K
C1107	NCB21HK-472X	C CAP.	4700pF 50V K
C1109	NCB21HK-472X	C CAP.	4700pF 50V K
C1110	NRSA02J-0R0X	MG R	0.0Ω 1/10W J
C1112	QETM1EM-476	E CAP.	47μF 25V M
C1113	NCB21HK-472X	C CAP.	4700pF 50V K
C1115	NCB21HK-103X	C CAP.	0.01μF 50V K

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C1116	NCB21HK-103X	C CAP.	0.01μF 50V K
C1117	QFV81HJ-224	MF CAP.	0.22μF 50V J
C1119	QETM1HM-474	E CAP.	0.47μF 50V M
C1120	NDC21HJ-121X	C CAP.	120pF 50V J
C1121	NCB21HK-103X	C CAP.	0.01μF 50V K
C1122	NCB21HK-103X	C CAP.	0.01μF 50V K
C1161	NCB21HK-103X	C CAP.	0.01μF 50V K
C1162	NCB21HK-152X	C CAP.	1500pF 50V K
C1164	NCB21HK-103X	C CAP.	0.01μF 50V K
C1165	NCB21HK-103X	C CAP.	0.01μF 50V K
C1166	NCB21HK-104X	C CAP.	0.1μF 50V K
C1301	NCB21HK-123X	C CAP.	0.012μF 50V K
C1302	QETM1HM-475	E CAP.	4.7μF 50V M
C1303	NDC21HJ-100X	C CAP.	10pF 50V J
C1304	QFV81HJ-474	MF CAP.	0.47μF 50V J
C1305	QETM1HM-474	E CAP.	0.47μF 50V M
C1306	NCB21HK-103X	C CAP.	0.01μF 50V K
C1307	QETM1CM-477	E CAP.	470μF 16V M
C1308	QETM1CM-107	E CAP.	100μF 16V M
C1309	NCB21HK-103X	C CAP.	0.01μF 50V K
C1310	NDC21HJ-221X	C CAP.	220pF 50V J
C1311	NCB21HK-103X	C CAP.	0.01μF 50V K
C1312	QENC1HM-474Z	E CAP.	0.47μF 50V M
C1313	QETM1HM-335Z	E CAP.	3.3μF 50V M
C1314	NCB21HK-103X	C CAP.	0.01μF 50V K
C1315	QETM1CM-107	E CAP.	100μF 16V M
C1316	QETM1HM-106	E CAP.	10μF 50V M
C1317	NCB21HK-473X	C CAP.	0.047μF 50V K
C1321	NDC21HJ-120X	C CAP.	12pF 50V J
C1322	NCB21HK-273X	C CAP.	0.027μF 50V K
C1323	QETM1HM-474	E CAP.	0.47μF 50V M
C1324	QETM1HM-106	E CAP.	10μF 50V M
C1325	QENB1HM-106	BP E CAP.	10μF 50V M
C1326	NCS21HJ-221X	C CAP.	220pF 50V J
C1341	QETM1HM-106	E CAP.	10μF 50V M
C1352	QFZ0097-103	MM CAP.	0.01μF 1250V K
C1354	NDC21HJ-221X	C CAP.	220pF 50V J
C1355	NDC21HJ-271X	C CAP.	270pF 50V J
C1356	NDC21HJ-331X	C CAP.	330pF 50V J
C1357	QETM1AM-477Z	E CAP.	470μF 10V M
C1365	QENB1HM-105	BP E CAP.	1μF 50V M
C1366	QENB1HM-105	BP E CAP.	1μF 50V M
C1367	QENB1HM-105	BP E CAP.	1μF 50V M
C1401	QFV81HJ-474	MF CAP.	0.47μF 50V J
C1402	QFV71HJ-104Z	MF CAP.	0.1μF 50V J
C1422	QETM1HM-105	E CAP.	1μF 50V M
C1423	QCS32HJ-100Z	C CAP.	10pF 500V J
C1424	QFLB2AJ-103	M CAP.	0.01μF 100V J
C1426	QFLB1HJ-103	M CAP.	0.01μF 50V J
C1427	QETM1VM-107	E CAP.	100μF 35V M
C1428	QEHQ1VM-107	E CAP.	100μF 35V M
C1429	QETM1HM-106	E CAP.	10μF 50V M
C1430	QFLC2AJ-272Z	M CAP.	2700pF 100V J
C1433	QEHQ1HM-475	E CAP.	4.7μF 50V M
C1435	QETM1EM-228	E CAP.	2200μF 25V M
C1436	QFV81HJ-334	MF CAP.	0.33μF 50V J
C1501	QETM1HM-476	E CAP.	47μF 50V M
C1502	NCB21HK-103X	C CAP.	0.01μF 50V K
C1503	QETM1HM-106	E CAP.	10μF 50V M
C1504	QETM1CM-227	E CAP.	220μF 16V M
C1523	QTMN1VM-476Z	E CAP.	47μF 35V M
△ C1525	QFZ0200-812	MPP CAP.	8100pF 1.5kVH±3%
C1526	QTMN1EM-337Z	E CAP.	330μF 25V M
△ C1527	QFZ0199-274	MPP CAP.	0.27μF 250V J
C1530	QCB32HK-561	C CAP.	560pF 500V K
C1531	QEZO203-107	E CAP.	100μF 160V M
C1552	QETM1VM-108	E CAP.	1000μF 35V M
C1554	QETM2EM-475	E CAP.	4.7μF 250V M
C1555	QFLC2AJ-104Z	M CAP.	0.1μF 100V J
C1571	QETM1AM-107	E CAP.	100μF 10V M
C1572	QETM1EM-476	E CAP.	47μF 25V M
C1581	QFV81HJ-104	MF CAP.	0.1μF 50V J
△ C1582	QFZ0199-274	MPP CAP.	0.27μF 250V J
C1651	QTN1CM-105Z	E CAP.	1μF 50V M
C1652	QEHQ1HM-106	E CAP.	10μF 50V M
C1653	QEHQ1HM-106	E CAP.	10μF 50V M
C1654	NCB21HK-104X	C CAP.	0.1μF 50V K

[AV-16N73_{NT}]

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

CAPACITOR

C1655	QEHQ1VM-228	E CAP.	2200μF 35V M
C1656	QEHQ1EM-477	E CAP.	470μF 25V M
C1658	QETM1HM-226	E CAP.	22μF 50V M
C1659	QETM1CM-107	E CAP.	100μF 16V M
C1663	QEHQ1HM-106	E CAP.	10μF 50V M
C1664	NCB21HK-104X	C CAP.	0.1μF 50V K
C1665	QEHRIHM-105Z	E CAP.	1μF 50V M
C1701	QETM1HM-106	E CAP.	10μF 50V M
C1705	QETM1CM-477	E CAP.	470μF 16V M
C1706	NCB21EK-104X	C CAP.	0.1μF 25V K
C1707	NCB21HK-103X	C CAP.	0.01μF 50V K
C1708	QETM1EM-476	E CAP.	47μF 25V M
C1709	NCB21HK-103X	C CAP.	0.01μF 50V K
C1710	QETM1CM-107	E CAP.	100μF 16V M
C1711	NCB21HK-103X	C CAP.	0.01μF 50V K
C1712	NCB21HK-103X	C CAP.	0.01μF 50V K
C1713	NCB21HK-103X	C CAP.	0.01μF 50V K
C1714	NDC21HJ-330X	C CAP.	330F 50V J
C1715	NDC21HJ-330X	C CAP.	330F 50V J
C1716	NDC21HJ-181X	C CAP.	1800F 50V J
C1717	NDC21HJ-181X	C CAP.	1800F 50V J
C1718	NCB21HK-103X	C CAP.	0.01μF 50V K
C1719	QETM1HM-105	E CAP.	1μF 50V M
C1720	NCB21HK-103X	C CAP.	0.01μF 50V K
C1721	NCB21HK-333X	C CAP.	0.033μF 50V K
C1722	NDC21HJ-101X	C CAP.	100pF 50V J
C1728	NDC21HJ-181X	C CAP.	1800F 50V J
C1729	NDC21HJ-181X	C CAP.	1800F 50V J
C1730	NCB21HK-103X	C CAP.	0.01μF 50V K
C1738	QETM1HM-226	E CAP.	22μF 50V M
C1744	NCB21HK-103X	C CAP.	0.01μF 50V K
C1805	QETM1CM-227	E CAP.	220μF 16V M
C1806	QETM1CM-477	E CAP.	470μF 16V M
C1811	QETM1HM-106	E CAP.	10μF 50V M
C1841	NCB21HK-152X	C CAP.	1500pF 50V K
△ C1901	QFZ9040-104	MF CAP.	0.1μFAC275V M
△ C1904	QCZ9082-222Z	C CAP.	2200pFAC250V M
△ C1905	QCZ9082-222Z	C CAP.	2200pFAC250V M
△ C1907	QCZ9082-222Z	C CAP.	2200pFAC250V M
C1909	QEZ0199-127	E CAP.	120μF 400V M
△ C1910	QFZ9040-473	MF CAP.	0.047μFAC275V M
C1922	QFLB1HJ-471	M CAP.	470pF 50V J
C1924	QETM1VM-107	E CAP.	100μF 35V M
C1926	QFLC1HJ-332Z	M CAP.	3300pF 50V J
C1928	NCB21HK-473X	C CAP.	0.047μF 50V K
C1929	QFP32GJ-223Z	PP CAP.	0.022μF 400V J
C1930	QCZ0325-561	C CAP.	560pF 2kV K
C1931	QCZ0325-151	C CAP.	150pF 2kV K
C1932	QCZ0325-151	C CAP.	150pF 2kV K
C1941	QCZ0122-561	C CAP.	560pF 2kV K
C1942	QEZ0420-107	E CAP.	100μF 160V M
C1945	QEHQ1CM-108	E CAPACITOR	1000μF 16V M
C1946	QEHRI1CM-477Z	E CAP.	470μF 16V M
C1948	QEHQ1VM-108	E CAP.	1000μF 35V M
C1949	NDC21HJ-471X	C CAP.	470pF 50V J
C1950	NCB21HK-104X	C CAP.	0.1μF 50V K
C1971	QETM1HM-226	E CAPACITOR	22μF 50V M
C1972	QETM1CM-107	E CAPACITOR	100μF 16V M
C1976	QETM1HM-105	E CAPACITOR	1μF 50V M
C1977	QETM1CM-477	E CAP.	470μF 16V M
C1978	QETM1CM-227	E CAPACITOR	22μF 16V M
C1979	QETM1CM-107	E CAPACITOR	100μF 16V M
△ C1991	QCZ9079-471	C CAP.	470pFAC250V K
△ C1992	QCZ9079-471	C CAP.	470pFAC250V K
△ C1993	QCZ9079-102	C CAP.	1000pFAC250V M

TRANSFORMER

△ T1522	QQH0072-001-KD	FBT	
△ T1921	QQS0050-001	SW TRANSF.	or QQS0056-001

COIL

L1001	QQL242K-8R2	COIL	8.2μH K
L1101	QQL2014-2R2	INDUCTOR	

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

COIL

L1103	QQL242K-8R2	COIL	8.2μH K
L1522	CE41807-00B	H. LTN. COIL	
L1523	QQL342J-2R2Z	INDUCTOR	
L1551	QQL2018-670	INDUCTOR	
L1701	QQL244J-5R6Z	COIL	5.6μH J
L1941	QQL26AK-820Z	COIL	82μH K
L1942	QQL26AK-820Z	COIL	82μH K
L1943	QQL26AK-820Z	COIL	82μH K

DIODE

D1001	MA3330/L/-X	ZENER DIODE	
D1102	MA859-T2	SI. DIODE	
D1301	MA3091/M/-X	ZENER DIODE	
D1302	MA3091/M/-X	ZENER DIODE	
D1305	RB100A-T2	SB DIODE	
D1306	1SR124-400A-T2	SI. DIODE	
D1341	MA111-X	SI. DIODE	
D1342	MA111-X	SI. DIODE	
D1421	MA3360/M/-X	ZENER DIODE	
D1422	MA3360/M/-X	ZENER DIODE	
D1423	1SR124-400A-T2	SI. DIODE	
D1424	MA111-X	SI. DIODE	
D1425	MA111-X	SI. DIODE	
D1427	MA3270/H/-X	ZENER DIODE	
D1551	RGP10J-TS-T3	SI. DIODE	
D1552	RH15-T3	SI. DIODE	
D1553	MA3091/M/-X	ZENER DIODE	
D1554	MA111-X	SI. DIODE	
D1571	MA3075/M/-X	ZENER DIODE	
D1581	MA3200/M/-X	ZENER DIODE	
D1582	RGP10J-TS-T3	SI. DIODE	
D1651	MA111-X	SI. DIODE	
D1652	MA111-X	SI. DIODE	
D1653	MTZJ18A-T2	ZENER DIODE	
D1701	MA111-X	SI. DIODE	
D1704	L-132XID-T16	LED	
D1705	L-132XND-T16	LED	
D1706	MA111-X	SI. DIODE	
D1707	MA111-X	SI. DIODE	
D1731	MA111-X	SI. DIODE	
△ D1901	G2SBA60	BRIDGE DIODE	
D1921	RGP10J-TS-T3	SI. DIODE	
D1922	MA111-X	SI. DIODE	
D1923	MA111-X	SI. DIODE	
D1924	MA111-X	SI. DIODE	
D1926	MA3056/M/-X	ZENER DIODE	
D1927	MA3068/M/-X	ZENER DIODE	
D1929	RD12E/B2/-T5	ZENER DIODE	
D1930	EG1A-T3	SI. DIODE	
D1932	MA111-X	SI. DIODE	
D1933	RD27E/B2/-T5	ZENER DIODE	
D1941	RU3AM-LFC4	SI. DIODE	
D1942	RU3YX-LFC4	SI. DIODE	
D1943	RGP10J-TS-T3	SI. DIODE	
△ D1945	MA3075/H/-X	ZENER DIODE	
D1973	MA111-X	SI. DIODE	
D1974	MA111-X	SI. DIODE	
D1982	MA111-X	SI. DIODE	
D1983	MA111-X	SI. DIODE	

TRANSISTOR

Q1102	2SC5083/L-P/-T	SI. TRANSISTOR	
Q1103	UN2212-X	DIGI. TRANSISTOR	
Q1161	2SD601A/QR/-X	SI. TRANSISTOR	
Q1301	2SB709A/QR/-X	SI. TRANSISTOR	
Q1302	2SD601A/QR/-X	SI. TRANSISTOR	
Q1351	2SC4722/NP/	SI. TRANSISTOR	
Q1352	2SC4722/NP/	SI. TRANSISTOR	
Q1353	2SC4722/NP/	SI. TRANSISTOR	
Q1401	DTC124ESA-T	DIGI. TRANSISTOR	
Q1402	2SD601A/QR/-X	SI. TRANSISTOR	
Q1521	2SK3065-W	MOS FET	
△ Q1522	2SC5388-CA	POWER TRANSISTOR	H. OUT
Q1523	2SD601A/QR/-X	SI. TRANSISTOR	
Q1524	2SD601A/QR/-X	SI. TRANSISTOR	
Q1571	2SA1208/ST/Z1-T	SI. TRANSISTOR	
Q1572	2SD601A/QR/-X	SI. TRANSISTOR	

[AV-16N73VT]

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

TRANSISTOR

Q1651	2SB709A/QR/-X	SI. TRANSISTOR	
Q1652	DTC323TK-X	DIGI. TRANSISTOR	
Q1654	2SD601A/QR/-X	SI. TRANSISTOR	
Q1655	2SD601A/QR/-X	SI. TRANSISTOR	
Q1702	2SD601A/QR/-X	SI. TRANSISTOR	
Q1703	2SD601A/QR/-X	SI. TRANSISTOR	
Q1708	UN2212-X	DIGI. TRANSISTOR	
Q1709	2SB709A/QR/-X	SI. TRANSISTOR	
Q1803	2SC1815/YG/-T	SI. TRANSISTOR	
Q1804	2SD601A/QR/-X	SI. TRANSISTOR	
Q1941	2SD601A/QR/-X	SI. TRANSISTOR	
Q1943	UN2211-X	DIGI. TRANSISTOR	
Q1973	2SD601A/QR/-X	SI. TRANSISTOR	
Q1974	2SA966/QY/-T	SI. TRANSISTOR	
Q1975	UN2212-X	DIGI. TRANSISTOR	

IC

IC1301	NN5198K	I C	
IC1421	AN5539-LF	I C	
IC1651	LA4287	I C	
IC1652	SI-5003X-X	I C	
△ IC1701	MN1873287JM	I C	
IC1702	AT24C08-21D73VT	I C	(SERVICE)
IC1703	L78LR05E-MA	I C	
IC1704	PIC-47143SY	IR DETECT UNIT	or PIC-28143SY
△ IC1921	STR-G6653	I C	
IC1941	SE115N-LF12	I C	
IC1971	BA51W12ST-V5	I C	

OTHERS

	LC30114-001C-H	LED HOLDER	
	CM35921-B02	CDS HOLDER	
△ CF1161	SF5H4.5MCB	CERAMIC FILTER	
△ CP1981	ICP-N75	C PROTECTOR	

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

OTHERS


△ CP1982	ICP-N75	C PROTECTOR	
△ F1901	QMF51E2-3R15J4	FUSE	3.15A
FC1901	CEMG002-001Z	FUSE CLIP	
J1002	QNN0384-001	PIN JACK	or CEMN075-001
J1003	QNN0281-003	PIN JACK	or CEMN065-001
J1004	QNN0281-002	PIN JACK	or CEMN065-002
△ J1005	QNS0165-001	3.5 JACK	
J1006	QNN0281-002	PIN JACK	or CEMN065-002
K1001	QQR0621-002Z	FERRITE BEADS	
K1351	QQR0621-002Z	FERRITE BEADS	
K1421	QQR0582-001Z	FERRITE BEADS	
K1921	QQR1113-001Z	FERRITE BEADS	
K1922	QQR1113-001Z	FERRITE BEADS	
K1923	QQR1114-001Z	FERRITE BEADS	
K1924	QQR1113-001Z	FERRITE BEADS	
K1941	QQR1113-001Z	FERRITE BEADS	
K1942	QQR1113-001Z	FERRITE BEADS	
K1943	QQR1113-001Z	FERRITE BEADS	
△ LF1901	QQR1095-002	LINE FILTER	
PC1701	P1241-04	PHOTO CONDUCTOR	
△ PC1921	PC123F2	IC (PHOTO COUPLE	or TLP721F (D4-GR)
△ RY1971	QSK0061-002	RELAY	or CESK028-001
S1701	QSW0619-003Z	TACT SWITCH	MENU
S1702	QSW0619-003Z	TACT SWITCH	CH-
S1703	QSW0619-003Z	TACT SWITCH	CH+
S1704	QSW0619-003Z	TACT SWITCH	VOL-
S1705	QSW0619-003Z	TACT SWITCH	VOL+
△ S1901	QSW0750-001	PUSH SWITCH	POWER SW
SF1102	QAX0594-001	SAW FILTER	
SF1122	QAX0325-001	SAW FILTER	
△ SK1351	CE42554-001	C R T SOCKET	
△ TH1901	QAD0119-9R0	THERMISTOR	or QAD0121-9R0
TU1001	QAU0186-002	TUNER	
△ VA1901	QAF0052-621	VARIATOR	or ERZV10V621CS
X1301	QAX0500-001Z	CRYSTAL	
X1302	CE42690-001Z	CRYSTAL	
X1701	FCR12.0M2S	CRYSTAL	

PACKING PARTS LIST

[AV-16N73/VT]

△ Ref.No.	Part No.	Part Name	Description
1	GG10007-022A-E	PACKING CASE	4pcs in 1set
2	GG10018-001A	CUSHION ASSY	
3	GG30033-001A-E	POLY BAG	
4	RM-C367GY-1H	REMOCON UNIT	
5	GG40015-001A-E	SERIAL LABEL	
6	GG30034-001A-E	POLY BAG	
△ 7	LCT1210-001A	INST BOOK	
8	CEAB005-00AJ1	MATCHING BOX	
9	CM35847-00B-H	ROD ANTENNA	

PACKING





JVC

VICTOR COMPANY OF JAPAN, LIMITED

HOME AV NETWORK BUSINESS UNIT 12, 3-chome, Moriya-cho, Kanagawa-ku, Yokohama, Kanagawa-prefecture, 221-8528, Japan



Printed in Japan
0208 WPC