

PARTS LIST

CAUTION

- The parts identified by the \triangle symbol are important for the safety . Whenever replacing these parts, be sure to use specified ones to secure the safety .
- The parts not indicated in this Parts List and those which are filled with lines --- in the Parts No. columns will not be supplied .
- P. W. Board Ass'y will not be supplied, but those which are filled with the Parts No. in the Parts No. columns will be supplied .

ABBREVIATIONS OF RESISTORS, CAPACITORS AND TOLERANCES

| RESISTORS | | CAPACITORS | |
|-----------|--|-----------------|---|
| C R | Carbon Resistor | C CAP. | Ceramic Capacitor |
| F R | Fusible Resistor | E CAP. | Electrolytic Capacitor |
| P R | Plate Resistor | M CAP. | Mylar Capacitor |
| V R | Variable Resistor | CH CAP. | Chip Capacitor |
| HV R | High Voltage Resistor | HV CAP. | High Voltage Capacitor |
| MF R | Metal Film Resistor | MF CAP. | Metalized Film Capacitor |
| MG R | Metal Glazed Resistor | MM CAP. | Metalized Mylar Capacitor |
| MP R | Metal Plate Resistor | MP CAP. | Metalized Polystyrol Capacitor |
| OM R | Metal Oxide Film Resistor | PP CAP. | Polypropylene Capacitor |
| CMF R | Coating Metal Film Resistor | PS CAP. | Polystyrol Capacitor |
| UNF R | Non-Flammable Resistor | TF CAP. | Thin Film Capacitor |
| CH V R | Chip Variable Resistor | MPP CAP. | Metalized Polypropylene Capacitor |
| CH MG R | Chip Metal Glazed Resistor | TAN. CAP. | Tantalum Capacitor |
| COMP. R | Composition Resistor | CH C CAP. | Chip Ceramic Capacitor |
| LPTC R | Linear Positive Temperature Coefficient Resistor | BP E CAP. | Bi-Polar Electrolytic Capacitor |
| | | CH AL E CAP. | Chip Aluminum Electrolytic Capacitor |
| | | CH AL BP CAP. | Chip Aluminum Bi-Polar Capacitor |
| | | CH TAN. E CAP. | Chip Tantalum Electrolytic Capacitor |
| | | CH AL BP E CAP. | Chip Tantalum Bi-Polar Electrolytic Capacitor |

| RESISTORS | | | | | | | | | |
|-----------|-----|-----|------|------|------|--------------|--------------|--------------|-------------|
| F | G | J | K | M | N | R | H | Z | P |
| ±1% | ±2% | ±5% | ±10% | ±20% | ±30% | +30% -10% | +50% -10% | +80% -20% | +100% 0% |

CONTENTS

| | |
|---|----|
| USING P.W. BOARD & REMOTE CONTROL UNIT | 41 |
| EXPLODED VIEW PARTS LIST-I | 41 |
| EXPLODED VIEW-I | 41 |
| EXPLODED VIEW PARTS LIST-II | 42 |
| EXPLODED VIEW-II | 43 |
| EXPLODED VIEW PARTS LIST-III [AV-29W33B/PH] | 44 |
| EXPLODED VIEW-III [AV-29W33B/PH] | 44 |

| | |
|--|----|
| PRINTED WIRING BOARD PARTS LIST [AV-29W33/PH] | |
| MAIN PW BOARD ASS'Y | 45 |
| CRT SOCKET PW BOARD ASS'Y | 49 |
| FRONT CONTROL PW BOARD ASS'Y | 51 |

| | |
|---|----|
| REMOTE CONTROL UNIT PARTS LIST (RM-C1019-1H) | 52 |
|---|----|

| | |
|---|--|
| PRINTED WIRING BOARD PARTS LIST [AV-29W33B/PH] | |
| MAIN PW BOARD ASS'Y | 53 |
| CRT SOCKET PW BOARD ASS'Y | Refer to PARTS LIST in pages 49-51 for this PW BOARD |
| FRONT CONTROL PW BOARD ASS'Y | Refer to PARTS LIST in pages 51-52 for this PW BOARD |

| | |
|---|----|
| REMOTE CONTROL UNIT PARTS LIST (RM-C1018-1H) | 58 |
|---|----|

| | |
|---|----|
| PACKING / PACKING PARTS LIST | 59 |
|---|----|


USING P.W. BOARD & REMOTE CONTROL UNIT

| P.W.B ASS'Y | Model | AV-29W33/PH | AV-29W33B/PH |
|---------------------|-------|--------------|--------------|
| MAIN PWB | | SCH-1117A-H2 | SCH-1083A-H2 |
| CRT SOCKET PWB | | SCH-3005A-H2 | ← |
| FRONT CONTROL PWB | | SCH-8004A-H2 | ← |
| REMOTE CONTROL UNIT | | RM-C1019-1H | RM-C1018-1H |

EXPLODED VIEW PARTS LIST-I

| △ Ref.No. | Part No. | Part Name | Description | Local |
|-----------|----------------|------------------|-------------------------|-------|
| 22 | GG20028-001A-H | OPERATION SHEET | | |
| 23 | GG30050-001B-H | REMOCON LENS | | |
| 24 | GG30049-001B-H | LED LENS | | |
| 25 | LC41037-003A-H | JVC MARK | | |
| 26 | GG10189-004A-H | FRONT CABI ASS'Y | Inc. No. 27, 28, 29, 30 | |
| 27 | GG20027-003B-H | DOOR | | |
| 28 | CM48229-00A-C | DOOR LATCH | | |
| 29 | GG30048-001B-H | POWER KNOB | | |
| 30 | CM35235-003-H | SPRING | | |


EXPLODED VIEW-I



EXPLODED VIEW PARTS LIST-II

| △ Ref.No. | Part No. | Part Name | Description | Local |
|-----------|----------------|---------------------|--------------------------------|-------|
| △ V01 | A68QCU257X75K | PICTURE TUBE (ITC) | Inc. DEF YOKE | |
| △ L01 | QQW0150-001 | DEG COIL | | |
| △ T1551 | QQH0139-001 | FBT | Not including ANODE WIRE ASS'Y | |
| 1 | LC11061-001A-H | CHASSIS BASE | | |
| 2 | LC11062-001D-H | CONTROL BASE | | |
| 3 | LC11064-003A-H | AV TERMINAL BOARD | [AV-29W33 _{PH}] | |
| 3 | LC11064-004A-H | AV TERMINAL BOARD | [AV-29W33B _{PH}] | |
| 4 | QYSBSF3012M | TAPPING SCREW | (X4) | |
| 5 | CHFD125-18BD | FFC WIRE | | |
| △ 6 | QMPR380-165-K2 | POWER CORD | | |
| △ 7 | CM23167-A01-H | POWER CORD CLAMP | | |
| 8 | LC30103-001B-H | CHASSIS ADAPTER | (X2) | |
| 9 | GG20023-001B-H | SP HOLDER | (X4) | |
| 10 | LC40226-003A-H | SPACER | (X4) | |
| 11 | LC40317-002A-H | TAPPING SCREW | (X4) | |
| 12 | QAS0114-001 | SPEAKER | (X2) | |
| 13 | WJY0018-001A | BRAIDED ASS'Y | | |
| 14 | CHGB0017-0C | BRAIDED ASS'Y (SUB) | (X2) | |
| 15 | A48457-3-H | SPRING | | |
| 16 | CE42568-00A | PC MAGNET | | |
| 17 | CE40764-00A | WEDGY ASS'Y | (X4) | |
| △ 18 | GG10192-002B-H | REAR COVER | [AV-29W33 _{PH}] | |
| △ 18 | GG10192-003B-H | REAR COVER | [AV-29W33B _{PH}] | |
| 19 | QYSBSFG4016Z | TAPPING SCREW | (X16) | |
| △ 20 | GG20024-001B-H | RATING LABEL | | |
| △ 21 | QNZ0369-001 | ANODE WIRE ASS'Y | | |


EXPLODED VIEW-II



EXPLODED VIEW PARTS LIST-Ⅲ [AV-29W33B/PH]

| △ Ref.No. | Part No. | Part Name | Description | Local |
|-----------|----------------|-------------------|-------------|-------|
| 31 | GG10140-001C-H | BASS TOP COVER | | |
| 32 | GG10141-001C-H | BASS BOTTOM COVER | | |
| 33 | QYSBSFG4016Z | TAPPING SCREW | (X13) | |
| 34 | GG20007-001C-H | BASS INT.DUCT R | (X2) | |
| 35 | GG20007-002C-H | BASS INT.DUCT L | (X2) | |
| 36 | QYSBSFG4016Z | TAPPING SCREW | (X6) | |
| 37 | GG30022-001A-H | BASS DUCT R | (X2) | |
| 38 | LC40352-001A-H | RUBBER SHEET | (X4) | |
| 39 | QAS0118-001 | BASS SPEAKER | | |
| 40 | QYSBSFG4016Z | TAPPING SCREW | (X4) | |
| 41 | LC41211-001A | SOUND ABSORBER | | |
| 42 | GG40028-001A-H | SEAL LABEL | | |

EXPLODED VIEW-Ⅲ [AV-29W33B/PH]



PRINTED WIRING BOARD PARTS LIST [AV-29W33/PH]

MAIN PW BOARD ASS'Y(SCH-1117A-H2)

| △ Symbol No. | Part No. | Part Name | Description | Local | △ Symbol No. | Part No. | Part Name | Description | Local |
|-----------------|--------------|-----------|---------------|-------|-----------------|---------------|-----------|---------------|-------|
| RESISTOR | | | | | RESISTOR | | | | |
| R1001 | NRSA63J-221X | MG R | 220Ω 1/16W J | | △ R1532 | QRZ9017-4R7 | F R | 4.7Ω 1/4W J | |
| R1002 | NRSA63J-221X | MG R | 220Ω 1/16W J | | R1541 | QRE121J-124Y | C R | 120kΩ 1/2W J | |
| R1003 | NRSA63J-392X | MG R | 3.9kΩ 1/16W J | | R1542 | QRE121J-124Y | C R | 120kΩ 1/2W J | |
| R1004 | NRSA63J-221X | MG R | 220Ω 1/16W J | | R1543 | QRE121J-471Y | C R | 470Ω 1/2W J | |
| R1005 | NRSA63J-273X | MG R | 27kΩ 1/16W J | | R1545 | QRE121J-220Y | C R | 22Ω 1/2W J | |
| R1006 | NRSA63J-750X | MG R | 75Ω 1/16W J | | R1546 | QRE121J-822Y | C R | 8.2kΩ 1/2W J | |
| R1101 | NRSA63J-100X | MG R | 10Ω 1/16W J | | △ R1547 | QRZ9011-4R7 | F R | 4.7Ω 1/2W J | |
| R1102 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | | R1561 | QRL029J-220 | OM R | 22Ω 2W J | |
| R1103 | NRSA63J-272X | MG R | 2.7kΩ 1/16W J | | R1562 | QRE121J-123Y | C R | 12kΩ 1/2W J | |
| R1104 | NRSA63J-181X | MG R | 180Ω 1/16W J | | R1563 | QRZ0056-103Z | COMP R | 10kΩ 1/2W K | |
| R1105 | NRSA63J-220X | MG R | 22Ω 1/16W J | | R1591 | QRA14CF-1202Y | CMF R | 12kΩ 1/4W F | |
| R1106 | NRSA63J-101X | MG R | 100Ω 1/16W J | | R1592 | QRZ0225-2R2 | UNF R | 2.2Ω 2W | |
| R1107 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | | R1593 | NRSA02F-332X | MG R | 3.3kΩ 1/10W F | |
| R1108 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | R1594 | QRE121J-183Y | C R | 18kΩ 1/2W J | |
| R1109 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | R1595 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1110 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | R1602 | NRSA63J-271X | MG R | 270Ω 1/16W J | |
| R1113 | NRSA63J-102X | MG R | 1kΩ 1/16W J | | R1603 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1114 | NRSA63J-102X | MG R | 1kΩ 1/16W J | | R1604 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1115 | NRSA63J-471X | MG R | 470Ω 1/16W J | | R1621 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1150 | NRSA63J-331X | MG R | 330Ω 1/16W J | | R1622 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1151 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | R1623 | NRSA63J-473X | MG R | 47kΩ 1/16W J | |
| R1152 | NRSA63J-121X | MG R | 120Ω 1/16W J | | R1624 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1153 | NRSA63J-122X | MG R | 1.2kΩ 1/16W J | | R1625 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1154 | NRSA63J-181X | MG R | 180Ω 1/16W J | | R1628 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1301 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | R1629 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1302 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | R1630 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1303 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | R1650 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1304 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | R1651 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1305 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | R1652 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1306 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | R1653 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R1307 | NRSA63J-103X | MG R | 10kΩ 1/16W J | | R1654 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1308 | NRSA63J-101X | MG R | 100Ω 1/16W J | | R1655 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R1309 | NRSA63J-473X | MG R | 47kΩ 1/16W J | | R1656 | QRE121J-2R2Y | C R | 2.2Ω 1/2W J | |
| R1310 | NRSA63J-473X | MG R | 47kΩ 1/16W J | | R1657 | QRE121J-2R2Y | C R | 2.2Ω 1/2W J | |
| R1311 | NRSA63J-123X | MG R | 12kΩ 1/16W J | | R1660 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1317 | QRL029J-101 | OM R | 100Ω 2W J | | R1661 | NRSA63J-683X | MG R | 68kΩ 1/16W J | |
| R1401 | NRSA63J-123X | MG R | 12kΩ 1/16W J | | R1662 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| R1403 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | | R1663 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1405 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | | R1664 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1406 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | | R1688 | NRSA63J-273X | MG R | 27kΩ 1/16W J | |
| R1408 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | | R1690 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R1410 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | | R1691 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1411 | QRG01GJ-221 | OM R | 220Ω 1W J | | R1695 | NRSA63J-153X | MG R | 15kΩ 1/16W J | |
| R1412 | QRE121J-1R0Y | C R | 1Ω 1/2W J | | R1696 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1413 | QRX01GJ-1R2 | MF R | 1.2Ω 1W J | | R1701 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1414 | QRE121J-2R2Y | C R | 2.2Ω 1/2W J | | R1702 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1425 | NRSA63J-153X | MG R | 15kΩ 1/16W J | | R1703 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1478 | NRSA63J-101X | MG R | 100Ω 1/16W J | | R1704 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1479 | NRSA63J-101X | MG R | 100Ω 1/16W J | | R1705 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1480 | QRE121J-681Y | C R | 680Ω 1/2W J | | R1706 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1481 | NRSA63J-223X | MG R | 22kΩ 1/16W J | | R1707 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| R1482 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | R1708 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| R1483 | NRSA63J-823X | MG R | 82kΩ 1/16W J | | R1709 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| R1484 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | R1710 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| R1485 | NRSA63J-123X | MG R | 12kΩ 1/16W J | | R1711 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1486 | NRSA63J-272X | MG R | 2.7kΩ 1/16W J | | R1712 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1487 | NRSA63J-333X | MG R | 33kΩ 1/16W J | | R1713 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1489 | NRSA63J-122X | MG R | 1.2kΩ 1/16W J | | R1714 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1490 | NRSA63J-102X | MG R | 1kΩ 1/16W J | | R1715 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1491 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | R1716 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1492 | NRSA63J-822X | MG R | 8.2kΩ 1/16W J | | R1717 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1493 | QRE121J-223Y | C R | 22kΩ 1/2W J | | R1718 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1494 | QRL039J-330 | OM R | 33Ω 3W J | | R1719 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1521 | NRSA63J-101X | MG R | 100Ω 1/16W J | | R1720 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1522 | NRSA63J-102X | MG R | 1kΩ 1/16W J | | R1721 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1523 | QRL039J-151 | OM R | 150Ω 3W J | | R1722 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1524 | QRL039J-151 | OM R | 150Ω 3W J | | R1723 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1526 | QRL029J-271 | OM R | 270Ω 2W J | | R1724 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1527 | QRL039J-103 | OM R | 10kΩ 3W J | | R1725 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| △ R1528 | QRZ9021-1R0 | F R | 1Ω 1W J | | R1726 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| △ R1529 | QRZ9021-1R0 | F R | 1Ω 1W J | | R1727 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R1531 | NRSA63J-182X | MG R | 1.8kΩ 1/16W J | | R1728 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|-----------------|--------------|-----------|---------------|-------|
| RESISTOR | | | | |
| R1730 | NRSA63J-223X | MG R | 22kΩ 1/16W J | |
| R1731 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1732 | NRSA02F-393X | MG R | 39kΩ 1/10W F | |
| R1733 | NRSA63J-273X | MG R | 27kΩ 1/16W J | |
| R1734 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| R1735 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R1736 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| R1737 | NRSA63J-272X | MG R | 2.7kΩ 1/16W J | |
| | | | | |
| R1738 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1739 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1740 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1741 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1742 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1744 | NRSA63J-561X | MG R | 560Ω 1/16W J | |
| R1745 | NRSA63J-105X | MG R | 1MΩ 1/16W J | |
| R1746 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| | | | | |
| R1747 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1748 | NRSA02J-225X | MG R | 2.2MΩ 1/10W J | |
| R1749 | NRSA02J-185X | MG R | 1.8MΩ 1/10W J | |
| R1750 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1755 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1756 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1757 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1758 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| | | | | |
| R1790 | NRSA63J-270X | MG R | 27Ω 1/16W J | |
| R1803 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| R1804 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1805 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1806 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1807 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1808 | NRSA63J-823X | MG R | 82kΩ 1/16W J | |
| R1809 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| | | | | |
| R1810 | NRSA63J-823X | MG R | 82kΩ 1/16W J | |
| R1811 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| R1812 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R1813 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1815 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1818 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1820 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1821 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| | | | | |
| R1823 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1824 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1826 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1829 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1830 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1831 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1832 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| R1833 | NRSA63J-271X | MG R | 270Ω 1/16W J | |
| | | | | |
| R1834 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | |
| R1835 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | |
| R1836 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1837 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1838 | QRK126J-121X | UNF R | 120Ω 1/2W J | |
| R1839 | QRE121J-221Y | C R | 220Ω 1/2W J | |
| R1840 | QRE121J-221Y | C R | 220Ω 1/2W J | |
| R1841 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| | | | | |
| R1842 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1843 | NRSA63J-821X | MG R | 820Ω 1/16W J | |
| R1844 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1845 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1846 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1847 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1848 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1849 | NRSA63J-471X | MG R | 470Ω 1/16W J | |
| | | | | |
| R1850 | QRE141J-0R0Y | C R | 0.0Ω 1/4W J | |
| R1880 | NRSA63J-202X | MG R | 2kΩ 1/16W J | |
| R1881 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1882 | NRSA63J-181X | MG R | 180Ω 1/16W J | |
| R1883 | NRSA63J-471X | MG R | 470Ω 1/16W J | |
| R1902 | QRF154K-2R2 | UNF R | 2.2Ω 15W K | |
| R1903 | QRL039J-393 | OM R | 39kΩ 3W J | |
| R1904 | QRE121J-221Y | C R | 220Ω 1/2W J | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|------------------|--------------|-----------|----------------|-------|
| RESISTOR | | | | |
| R1905 | QRM034J-R10 | MP R | 0.1Ω 3W J | |
| R1906 | QRE141J-1R5Y | C R | 1.5Ω 1/4W J | |
| R1908 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1911 | QRE121J-152Y | C R | 1.5kΩ 1/2W J | |
| R1912 | QRE121J-123Y | C R | 12kΩ 1/2W J | |
| △ R1913 | QRZ9017-100 | F R | 10Ω 1/4W J | |
| R1914 | QRL039J-473 | OM R | 47kΩ 3W J | |
| R1915 | NRSA63J-823X | MG R | 82kΩ 1/16W J | |
| | | | | |
| R1916 | NRSA63J-154X | MG R | 150kΩ 1/16W J | |
| R1951 | QRE121J-223Y | C R | 22kΩ 1/2W J | |
| R1952 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1953 | QRE121J-152Y | C R | 1.5kΩ 1/2W J | |
| R1954 | QRE121J-150Y | C R | 15Ω 1/2W J | |
| R1955 | QRG01GJ-330 | OM R | 33Ω 1W J | |
| R1956 | QRE121J-120Y | C R | 12Ω 1/2W J | |
| R1957 | QRE121J-5R6Y | C R | 5.6Ω 1/2W J | |
| | | | | |
| R1958 | QRL039J-820 | OM R | 82Ω 3W J | |
| R1959 | QRE121J-820Y | C R | 82Ω 1/2W J | |
| R1960 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| R1961 | QRL029J-223 | OM R | 22kΩ 2W J | |
| R1962 | NRSA63J-681X | MG R | 680Ω 1/16W J | |
| R1963 | QRE121J-332Y | C R | 3.3kΩ 1/2W J | |
| R1964 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1965 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| | | | | |
| R1966 | NRSA63J-223X | MG R | 22kΩ 1/16W J | |
| R1967 | NRSA63J-473X | MG R | 47kΩ 1/16W J | |
| R1968 | NRSA63J-331X | MG R | 330Ω 1/16W J | |
| R1969 | QRT029J-1R5 | MF R | 1.5Ω 2W J | |
| R1970 | NRSA63J-153X | MG R | 15kΩ 1/16W J | |
| R1971 | NRSA63J-183X | MG R | 18kΩ 1/16W J | |
| R1972 | QRE121J-182Y | C R | 1.8kΩ 1/2W J | |
| R1973 | QRE121J-332Y | C R | 3.3kΩ 1/2W J | |
| | | | | |
| △ R1974 | QRT029J-1R2 | MF R | 1.2Ω 2W J | |
| △ R1991 | QRZ0057-825 | C R | 8.2MΩ 1W J | |
| CAPACITOR | | | | |
| C1001 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1002 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1003 | QFV71HJ-104Z | MF CAP. | 0.1μF 50V J | |
| C1004 | QETN1CM-477Z | E CAP. | 470μF 16V M | |
| C1005 | NCB31HK-222X | C CAP. | 2200pF 50V K | |
| C1006 | QETN1CM-336Z | E CAP. | 33μF 16V M | |
| C1007 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1101 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| | | | | |
| C1102 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| C1103 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| C1104 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| C1106 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1107 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1109 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1150 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| C1151 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| | | | | |
| C1301 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1302 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1304 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1305 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1306 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1307 | NDC31HJ-330X | C CAP. | 33pF 50V J | |
| C1308 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1315 | QFLC1HJ-473Z | M CAP. | 0.047μF 50V J | |
| | | | | |
| C1401 | QETN1HM-336Z | E CAP. | 33μF 50V M | |
| C1402 | QCB31HK-682Z | C CAP. | 6800pF 50V K | |
| C1403 | QEHR1VM-107Z | E CAP. | 100μF 35V M | |
| C1406 | QFLC2AJ-683Z | M CAP. | 0.068μF 100V J | |
| C1407 | QCS32HJ-180Z | C CAP. | 18pF 500V J | |
| C1411 | NCF21HZ-334X | C CAP. | 0.33μF 50V Z | |
| C1412 | NCF21HZ-334X | C CAP. | 0.33μF 50V Z | |
| C1413 | QFLC2AJ-563Z | M CAP. | 0.056μF 100V J | |

| △ Symbol No. | Part No. | Part Name | Description | Local | △ Symbol No. | Part No. | Part Name | Description | Local |
|------------------|--------------|-----------|-------------------|-------|------------------|--------------|-----------|---------------|-------|
| CAPACITOR | | | | | CAPACITOR | | | | |
| C1422 | QEHQ1VM-108 | E CAP. | 1000μF 35V M | | C1652 | QETN1HM-105Z | E CAP. | 1μF 50V M | |
| C1471 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1653 | NCF21HZ-224X | C CAP. | 0.22μF 50V Z | |
| C1480 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1654 | NCF21HZ-224X | C CAP. | 0.22μF 50V Z | |
| C1483 | QEZ0195-475Z | BP E CAP. | 4.7μF 50V M | | C1655 | NCF21HZ-224X | C CAP. | 0.22μF 50V Z | |
| C1485 | QETN1HM-226Z | E CAP. | 22μF 50V M | | C1656 | NCF21HZ-224X | C CAP. | 0.22μF 50V Z | |
| C1521 | QETN1VM-476Z | E CAP. | 47μF 35V M | | C1662 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1522 | QFLC1HJ-332Z | M CAP. | 3300pF 50V J | | C1681 | QETN1CM-227Z | E CAP. | 220μF 16V M | |
| C1523 | QFLC1HJ-223Z | M CAP. | 0.022μF 50V J | | C1682 | QETN1CM-227Z | E CAP. | 220μF 16V M | |
| C1524 | QFZ0196-382 | MPP CAP. | 3800pF 1.5kVH±3% | | C1683 | QETN1CM-336Z | E CAP. | 33μF 16V M | |
| C1525 | QFZ0200-143 | MPP CAP. | 0.014μF 1.5kVH±3% | | C1684 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1526 | QFP32JJ-223 | PP CAP. | 0.022μF 630V J | | C1702 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1527 | QFZ0199-224 | MPP CAP. | 0.22μF AC250V J | | C1703 | NDC31HJ-330X | C CAP. | 33pF 50V J | |
| C1528 | QFZ0199-224 | MPP CAP. | 0.22μF AC250V J | | C1704 | NDC31HJ-330X | C CAP. | 33pF 50V J | |
| C1529 | QENC2AM-225Z | BP E CAP. | 2.2μF 100V M | | C1706 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C1530 | QCB32HK-561Z | C CAP. | 560pF 500V K | | C1707 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1531 | QEHR1EM-108Z | E CAP. | 1000μF 25V M | | C1709 | QETN1CM-477Z | E CAP. | 470μF 16V M | |
| C1532 | QCB32HK-561Z | C CAP. | 560pF 500V K | | C1710 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C1533 | QEHR1EM-108Z | E CAP. | 1000μF 25V M | | C1711 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1534 | QCB32HK-561Z | C CAP. | 560pF 500V K | | C1712 | QETN1CM-476Z | E CAP. | 47μF 16V M | |
| C1536 | QFLC1HJ-103Z | M CAP. | 0.01μF 50V J | | C1713 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1540 | QFV71HJ-104Z | MF CAP. | 0.1μF 50V J | | C1720 | QETN1EM-476Z | E CAP. | 47μF 25V M | |
| C1541 | QETN2EM-106Z | E CAP. | 10μF 250V M | | C1725 | NCB31HK-681X | C CAP. | 680pF 50V K | |
| C1550 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1729 | QETN1CM-476Z | E CAP. | 47μF 16V M | |
| C1561 | QFV21HJ-154Z | MF CAP. | 0.15μF 50V J | | C1730 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C1566 | QFZ0200-113 | MPP CAP. | 0.011μF 1.5kVH±3% | | C1731 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C1591 | QETN1CM-107Z | E CAP. | 100μF 16V M | | C1732 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1592 | QETM2CM-227 | E CAP. | 220μF 160V M | | C1733 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1593 | QETN1EM-476Z | E CAP. | 47μF 25V M | | C1734 | NCB31HK-222X | C CAP. | 2200pF 50V K | |
| C1602 | NCB31HK-103X | C CAP. | 0.01μF 50V K | | C1735 | NCB31HK-222X | C CAP. | 2200pF 50V K | |
| C1603 | QETN1CM-107Z | E CAP. | 100μF 16V M | | C1736 | QETN1HM-105Z | E CAP. | 1μF 50V M | |
| C1604 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1737 | QETN1HM-105Z | E CAP. | 1μF 50V M | |
| C1606 | NDC31HJ-2R0X | C CAP. | 2.0pF 50V J | | C1738 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1607 | NDC31HJ-2R0X | C CAP. | 2.0pF 50V J | | C1739 | NFV41CJ-104X | MPP CAP. | 0.1μF 16V J | |
| C1608 | NCB31HK-103X | C CAP. | 0.01μF 50V K | | C1740 | QETN1HM-225Z | E CAP. | 2.2μF 50V M | |
| C1609 | NCB31HK-103X | C CAP. | 0.01μF 50V K | | C1741 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1610 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1742 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1611 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1743 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1612 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1744 | NCB31HK-222X | C CAP. | 2200pF 50V K | |
| C1613 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1745 | NCB31HK-473X | C CAP. | 0.047μF 50V K | |
| C1615 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1747 | NCB31HK-473X | C CAP. | 0.047μF 50V K | |
| C1616 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1749 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1617 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1751 | NCB21HK-104X | C CAP. | 0.1μF 50V K | |
| C1618 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1752 | NCB21HK-104X | C CAP. | 0.1μF 50V K | |
| C1619 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1753 | NCB21HK-104X | C CAP. | 0.1μF 50V K | |
| C1620 | NCB31HK-102X | C CAP. | 1000pF 50V K | | C1801 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1621 | NCB31HK-102X | C CAP. | 1000pF 50V K | | C1802 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1625 | NCF21EZ-474X | C CAP. | 0.47μF 25V Z | | C1803 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1626 | NCB31HK-333X | C CAP. | 0.033μF 50V K | | C1804 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1627 | NCB31HK-473X | C CAP. | 0.047μF 50V K | | C1805 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1628 | NCB31HK-223X | C CAP. | 0.022μF 50V K | | C1807 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1629 | NCB31HK-222X | C CAP. | 2200pF 50V K | | C1808 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1630 | NCB31HK-104X | C CAP. | 0.1μF 50V K | | C1810 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1631 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1811 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1632 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1812 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1633 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1813 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1634 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1814 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1635 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1815 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1636 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1817 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1637 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1819 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1638 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1820 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1639 | QETN1HM-107Z | E CAP. | 100μF 50V M | | C1821 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1640 | NCF21HZ-334X | C CAP. | 0.33μF 50V Z | | C1822 | QETN1CM-477Z | E CAP. | 470μF 16V M | |
| C1641 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1823 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1643 | NCB31HK-104X | C CAP. | 0.1μF 50V K | | C1824 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1644 | NCB31HK-222X | C CAP. | 2200pF 50V K | | C1825 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1645 | NCB31HK-104X | C CAP. | 0.1μF 50V K | | C1826 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1646 | NCB31HK-104X | C CAP. | 0.1μF 50V K | | C1827 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1647 | NCF21EZ-474X | C CAP. | 0.47μF 25V Z | | C1829 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1648 | NCB31HK-153X | C CAP. | 0.015μF 50V K | | C1830 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1649 | NCB31HK-153X | C CAP. | 0.015μF 50V K | | C1831 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1650 | NCF31AZ-105X | C CAP. | 1μF 10V Z | | C1833 | QETN1HM-226Z | E CAP. | 22μF 50V M | |
| C1651 | QEHR1HM-107Z | E CAP. | 100μF 50V M | | C1834 | NDC31HJ-181X | C CAP. | 180pF 50V J | |

| △ | Symbol No. | Part No. | Part Name | Description | Local |
|------------------|------------|--------------|-----------|---------------|-------|
| CAPACITOR | | | | | |
| △ | C1902 | QFZ9072-104 | MM CAP. | 0.1μF | |
| | C1903 | QCZ9015-102Z | C CAP. | 1000pF AC250V | Z |
| | C1904 | QCZ9015-102Z | C CAP. | 1000pF AC250V | Z |
| | C1905 | QCZ9015-102Z | C CAP. | 1000pF AC250V | Z |
| | C1907 | QEZ0371-337 | E CAP. | 330μF 400V | M |
| | C1909 | QCZ0325-102 | C CAP. | 1000pF 2000V | K |
| | C1910 | NDC31HJ-102X | C CAP. | 1000pF 50V | J |
| | C1911 | QETN1VM-107Z | E CAP. | 100μF 35V | M |
| | | | | | |
| | C1913 | QFLC1HJ-683Z | M CAP. | 0.068μF 50V | J |
| | C1915 | QCB32HK-222Z | C CAP. | 2200pF 500V | K |
| | C1916 | QETN1HM-475Z | E CAP. | 4.7μF 50V | M |
| | C1917 | QCB32HK-181Z | C CAP. | 180pF 500V | K |
| | C1918 | QCB32HK-103 | C CAP. | 0.01μF 500V | K |
| | C1919 | QCZ0325-391 | C CAP. | 390pF 2000V | K |
| | C1920 | QCZ0122-471 | C CAP. | 470pF 2000V | K |
| | C1921 | QFN31HJ-473Z | M CAP. | 0.047μF 50V | J |
| | | | | | |
| | C1922 | QETN2AM-226Z | E CAP. | 22μF 100V | M |
| | C1952 | QCB32HK-471Z | C CAP. | 470pF 500V | K |
| | C1953 | QEHQ1VM-228 | E CAP. | 2200μF 35V | M |
| | C1955 | QCB32HK-471Z | C CAP. | 470pF 500V | K |
| | C1956 | QETN1VM-107Z | E CAP. | 100μF 35V | M |
| | C1957 | QCB31HK-471Z | C CAP. | 470pF 50V | K |
| | C1958 | QEHR1CM-108Z | E CAP. | 1000μF 16V | M |
| | C1959 | QCZ0364-561 | C CAP. | 560pF | |
| | | | | | |
| | C1960 | QEZ0203-227 | E CAP. | 220μF 160V | M |
| | C1961 | QETN1CM-476Z | E CAP. | 47μF 16V | M |
| | C1962 | QETN1HM-106Z | E CAP. | 10μF 50V | M |
| | C1963 | QETN1CM-477Z | E CAP. | 470μF 16V | M |
| | C1964 | QETN1EM-476Z | E CAP. | 47μF 25V | M |
| | C1965 | QETN1VM-476Z | E CAP. | 47μF 35V | M |
| | C1966 | QETN1CM-107Z | E CAP. | 100μF 16V | M |
| | C1968 | NCB31CK-104X | C CAP. | 0.1μF 16V | K |
| | | | | | |
| | C1970 | QETN1CM-107Z | E CAP. | 100μF 16V | M |
| | C1972 | QETN1EM-476Z | E CAP. | 47μF 25V | M |
| | C1974 | NCB31CK-104X | C CAP. | 0.1μF 16V | K |
| | C1975 | QETN1CM-227Z | E CAP. | 220μF 16V | M |
| | C1977 | QETN1EM-476Z | E CAP. | 47μF 25V | M |
| | C1978 | NCB21HK-104X | C CAP. | 0.1μF 50V | K |
| | C1980 | QETN1CM-107Z | E CAP. | 100μF 16V | M |
| | C1981 | NCB31HK-102X | C CAP. | 1000pF 50V | K |
| | | | | | |
| | C1982 | QETN1CM-476Z | E CAP. | 47μF 16V | M |
| | C1983 | QETN1CM-227Z | E CAP. | 220μF 16V | M |
| △ | C1991 | QCZ9079-102 | C CAP. | 1000pF AC250V | M |
| △ | C1992 | QCZ9079-102 | C CAP. | 1000pF AC250V | M |
| △ | C1993 | QCZ9079-102 | C CAP. | 1000pF AC250V | M |

TRANSFORMER

| | | | |
|---|-------|-------------|------------------|
| | T1521 | QQR1229-001 | DRIVE TRANSF |
| △ | T1551 | QQH0139-001 | FBT(HV WIRELESS) |
| | T1561 | QQR1153-001 | DEF TRANSF |
| △ | T1901 | QQS0110-001 | SW TRANSF |

COIL

| | | | | | |
|--|-------|--------------|----------------|--------|---|
| | L1001 | QQL244K-8R2Z | COIL | 8.2μH | K |
| | L1002 | QQL244K-8R2Z | COIL | 8.2μH | K |
| | L1101 | QQL244J-5R6Z | COIL | 5.6μH | J |
| | L1102 | QQL244K-180Z | COIL | 18μH | K |
| | L1301 | QQL244K-221Z | PEAKING COIL | 220μH | K |
| | L1401 | QQL26AK-220Z | COIL | 22μH | K |
| | L1480 | QQR1138-001 | CHOKE COIL | | |
| | L1523 | QQR1243-001 | LINEARITY COIL | | |
| | | | | | |
| | L1541 | QQL244K-220Z | COIL | 22μH | K |
| | L1561 | QQLZ028-272 | COIL | 2700μH | |
| | L1601 | QQL244K-4R7Z | COIL | 4.7μH | K |
| | L1701 | QQL244K-100Z | COIL | 10μH | K |
| | L1702 | QQL244K-100Z | COIL | 10μH | K |
| | L1731 | QQL244J-101Z | COIL | 100μH | J |
| | L1951 | QQLZ034-460 | COIL | 46μH | |
| | L1953 | QQL244J-5R6Z | COIL | 5.6μH | J |
| | | | | | |
| | L1954 | QQL26AK-820Z | COIL | 82μH | K |

| △ | Symbol No. | Part No. | Part Name | Description | Local |
|--------------|------------|----------------|--------------|-------------|---------|
| DIODE | | | | | |
| | D1101 | DAN235K-X | SI. DIODE | | |
| | D1301 | MTZJ5.1B-T2 | ZENER DIODE | | |
| | D1401 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1402 | MTZJ75-T2 | ZENER DIODE | | |
| | D1405 | 1N4003-T2 | SI. DIODE | | |
| | D1408 | MA111-X | SI. DIODE | | |
| | D1480 | MTZJ4.3A-T2 | ZENER DIODE | | |
| | D1521 | RH3G-F1 | SI. DIODE | | |
| | | | | | |
| | D1522 | 31DF6N-FC5 | SI. DIODE | | |
| | D1523 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1541 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1550 | MA111-X | SI. DIODE | | |
| | D1551 | EU2-T3 | SI. DIODE | | |
| | D1553 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1554 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1592 | MA3075/H-X | ZENER DIODE | | |
| | | | | | |
| | D1652 | MA3330/L-X | ZENER DIODE | | |
| | D1653 | MA3330/L-X | ZENER DIODE | | |
| | D1655 | MA111-X | SI. DIODE | | |
| | D1657 | MA111-X | SI. DIODE | | |
| | D1701 | MA111-X | SI. DIODE | | |
| | D1702 | MA3020-X | ZENER DIODE | | |
| | D1703 | MA3036-X | ZENER DIODE | | |
| | D1730 | MA111-X | SI. DIODE | | |
| | | | | | |
| | D1731 | MA111-X | SI. DIODE | | |
| | D1732 | MA111-X | SI. DIODE | | |
| | D1733 | MA111-X | SI. DIODE | | |
| | D1801 | MA3120/M-X | ZENER DIODE | | |
| | D1802 | MA3120/M-X | ZENER DIODE | | |
| | D1901 | GSIB460 | BRIDGE DIODE | | |
| | D1902 | MTZJ33B-T2 | ZENER DIODE | | |
| | D1906 | MTZJ27B-T2 | ZENER DIODE | | |
| | | | | | |
| | D1907 | MTZJ33B-T2 | ZENER DIODE | | |
| | D1908 | MA3200/M-X | ZENER DIODE | | |
| | D1909 | 1SS133-T2 | SI. DIODE | | |
| | D1911 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1912 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1913 | RGP10M-5010-T3 | SI. DIODE | | |
| | D1914 | NRSA63J-0R0X | MG R | 0.0Ω | 1/16W J |
| | D1915 | MTZJ39B-T2 | ZENER DIODE | | |
| | | | | | |
| | D1916 | MTZJ15B-T2 | ZENER DIODE | | |
| | D1917 | 1SS133-T2 | SI. DIODE | | |
| | D1919 | 1SS133-T2 | SI. DIODE | | |
| | D1920 | MTZJ15B-T2 | ZENER DIODE | | |
| | D1950 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1952 | ERC30-02L38 | SI. DIODE | | |
| | D1953 | RGP10J-5025-T3 | SI. DIODE | | |
| | D1954 | RU30A-F1 | SI. DIODE | | |
| | | | | | |
| | D1955 | 1SR35-400A-T2 | SI. DIODE | | |
| | D1956 | 31DF6N-FC5 | SI. DIODE | | |
| | D1958 | MTZJ5.1A-T2 | ZENER DIODE | | |
| | D1959 | IM-BW | BUS WIRE | | |
| | D1960 | MA111-X | SI. DIODE | | |
| | D1964 | MA3330/L-X | ZENER DIODE | | |
| | D1966 | MA3047/L-X | ZENER DIODE | | |
| | D1968 | MA111-X | SI. DIODE | | |
| | | | | | |
| | D1969 | MA111-X | SI. DIODE | | |
| | D1970 | MTZJ9.1B-T2 | ZENER DIODE | | |
| | D1971 | NRSA02J-0R0X | MG R | 0.0Ω | 1/10W J |

TRANSISTOR

| | | |
|-------|---------------|------------------|
| Q1101 | 2SC5083/L-P/T | TRANSISTOR |
| Q1106 | 2SB709A/QR/-X | TRANSISTOR |
| Q1108 | 2SD601A/QR/-X | TRANSISTOR |
| Q1150 | 2SD601A/QR/-X | TRANSISTOR |
| Q1301 | 2SB709A/QR/-X | TRANSISTOR |
| Q1302 | 2SB709A/QR/-X | TRANSISTOR |
| Q1303 | UN2212-X | DIGI. TRANSISTOR |
| Q1304 | 2SD601A/QR/-X | TRANSISTOR |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|-------------------|-----------------|------------------|--------------|-------|
| TRANSISTOR | | | | |
| Q1480 | 2SD1408/OY/-LB | POW TRANSISTOR | | |
| Q1521 | 2SC2655/Y/-T | TRANSISTOR | | |
| Q1522 | 2SD2634-YD | POW TRANSISTOR | | |
| Q1591 | 2SA1208/ST/Z1-T | TRANSISTOR | | |
| Q1592 | UN2212-X | DIGI. TRANSISTOR | | |
| Q1660 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1661 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1683 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1684 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1685 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1686 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1701 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1702 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1720 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1801 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1802 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1803 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1804 | 2SC1740S/QR/-T | TRANSISTOR | | |
| Q1860 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1861 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1862 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1901 | 2SC3852A | POW TRANSISTOR | | |
| Q1951 | 2SA1013/RO/-T | TRANSISTOR | | |
| Q1952 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1953 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1954 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1955 | 2SD601A/QR/-X | TRANSISTOR | | |
| IC | | | | |
| IC1301 | TDA9181T/N1-X | I.C(MONO-ANA) | | |
| IC1401 | LA78041 | I.C(MONO-ANA) | | |
| IC1461 | JLC1562BF-X | I.C(DIGI-MOS) | | |
| IC1480 | UPC358G2-XE | IC(MONOLITHIC) | | |
| IC1601 | MSP3445G-QG-B8X | I.C(MONO-ANA) | | |
| IC1602 | NJW1136G-X | I.C(MONO-ANA) | | |
| IC1650 | AN5277 | I.C(MONO-ANA) | | |
| IC1701 | TDA9386N2310956 | I.C(MCU) | | |
| IC1702 | AT24C08-25L33PH | I.C(MEMORY-OTH) | (SERVICE) | |
| IC1801 | MM1492AF | I.C(MONO-ANA) | | |
| IC1901 | STR-F6256S-F7 | I.C(HYBRID) | | |
| IC1951 | SE135N | I.C(HYBRID) | | |
| IC1972 | L88M33T-X | I.C(MONO-ANA) | | |
| IC1973 | BA17812T | I.C(MONO-ANA) | | |
| IC1974 | BA51W12ST-V5 | I.C(MONO-ANA) | | |
| OTHERS | | | | |
| CF1103 | QAX0639-001Z | C TRAP | | |
| △ CP1951 | ICP-N75-Y | IC PROTECTOR | | |
| △ CP1952 | ICP-N38-Y | IC PROTECTOR | | |
| △ CP1953 | ICP-N38-Y | IC PROTECTOR | | |
| J1801 | QNN0349-001 | PIN JACK | | |
| J1802 | QNN0349-002 | PIN JACK | | |
| J1803 | QNN0348-001 | PIN JACK | | |
| J1804 | QNN0349-001 | PIN JACK | | |
| K1705 | QQR1214-001Y | FERRITE BEADS | | |
| K1901 | QQR1214-001Y | FERRITE BEADS | | |
| K1902 | QQR1214-001Y | FERRITE BEADS | | |
| K1903 | QQR1214-001Y | FERRITE BEADS | | |
| K1951 | QQR1214-001Y | FERRITE BEADS | | |
| K1953 | QQR1214-001Y | FERRITE BEADS | | |
| K1954 | QQR1214-001Y | FERRITE BEADS | | |
| K1955 | QQR1214-001Y | FERRITE BEADS | | |
| △ LF1901 | QQR1356-001 | LINE FILTER | | |
| △ PC1901 | PC123F2 | IC(PHOTO COUPLE) | | |
| △ RY1901 | QSK0061-001 | RELAY | | |
| SF1101 | QAX0663-001 | SAW FILTER | | |
| SF1102 | QAX0594-001 | SAW FILTER | | |
| TH1901 | QAD0145-2R3 | P THERMISTOR | | |
| TU1001 | QAU0251-002 | TUNER | | |
| W1010 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|---------------|--------------|---------------|--------------|-------|
| OTHERS | | | | |
| W1031 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1239 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1257 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1306 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1307 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1309 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1321 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1325 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1326 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1333 | QQR1113-001Z | FERRITE BEADS | | |
| W1334 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1379 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1386 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1395 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1397 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1402 | QQR1113-001Z | FERRITE BEADS | | |
| W1405 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1418 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1423 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1428 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1430 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1431 | QQR1113-001Z | FERRITE BEADS | | |
| X1601 | CE42546-001Z | X TAL | | |
| X1701 | QAX0737-001 | CRYSTAL | | |
| Y1004 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| Y1602 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| Y1603 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |

CRT SOCKET PW BOARD ASS'Y (SCH-3005A-H2)

| △ Symbol No. | Part No. | Part Name | Description | Local |
|-----------------|--------------|-----------|---------------|-------|
| RESISTOR | | | | |
| R3101 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | |
| R3102 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3103 | NRSA63J-153X | MG R | 15kΩ 1/16W J | |
| R3104 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | |
| R3105 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3106 | NRSA63J-272X | MG R | 2.7kΩ 1/16W J | |
| R3107 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | |
| R3108 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3109 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | |
| R3110 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3111 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3112 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3113 | NRSA63J-563X | MG R | 56kΩ 1/16W J | |
| R3120 | QRE121J-101Y | C R | 100Ω 1/2W J | |
| R3121 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3122 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3123 | QRE121J-152Y | C R | 1.5kΩ 1/2W J | |
| R3124 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R3125 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3126 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3127 | QRE121J-152Y | C R | 1.5kΩ 1/2W J | |
| R3128 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R3129 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3130 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3131 | QRE121J-152Y | C R | 1.5kΩ 1/2W J | |
| R3132 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R3133 | NRSA63J-470X | MG R | 47Ω 1/16W J | |
| R3136 | NRSA63J-470X | MG R | 47Ω 1/16W J | |
| R3137 | NRSA63J-470X | MG R | 47Ω 1/16W J | |
| R3138 | QRL029J-223 | OM R | 22kΩ 2W J | |
| R3139 | QRL029J-223 | OM R | 22kΩ 2W J | |
| R3140 | QRZ0107-102Z | C R | 1kΩ 1W K | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|-----------------|--------------|-----------|---------------|-------|
| RESISTOR | | | | |
| R3141 | QRL029J-223 | OM R | 22kΩ 2W J | |
| R3143 | QRL029J-223 | OM R | 22kΩ 2W J | |
| R3144 | QRZ0107-102Z | C R | 1kΩ 1W K | |
| R3145 | QRL029J-223 | OM R | 22kΩ 2W J | |
| R3146 | QRL029J-223 | OM R | 22kΩ 2W J | |
| R3147 | QRZ0107-102Z | C R | 1kΩ 1W K | |
| R3148 | QRE121J-124Y | C R | 120kΩ 1/2W J | |
| R3149 | QRE121J-102Y | C R | 1kΩ 1/2W J | |
| | | | | |
| R3151 | QRE121J-124Y | C R | 120kΩ 1/2W J | |
| R3152 | QRE121J-102Y | C R | 1kΩ 1/2W J | |
| R3153 | QRE121J-124Y | C R | 120kΩ 1/2W J | |
| R3154 | QRE121J-102Y | C R | 1kΩ 1/2W J | |
| R3155 | QRE121J-474Y | C R | 470kΩ 1/2W J | |
| R3157 | QRZ0107-474Z | C R | 470kΩ 1W K | |
| R3159 | NRSA63J-184X | MG R | 180kΩ 1/16W J | |
| R3161 | QRE121J-333Y | C R | 33kΩ 1/2W J | |
| | | | | |
| R3164 | QRE121J-560Y | C R | 56Ω 1/2W J | |
| R3166 | QRE121J-333Y | C R | 33kΩ 1/2W J | |
| R3167 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R3168 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R3170 | NRSA63J-332X | MG R | 3.3kΩ 1/16W J | |
| R3171 | NRSA63J-681X | MG R | 680Ω 1/16W J | |
| R3172 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R3173 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| | | | | |
| R3174 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R3211 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R3212 | NRSA63J-153X | MG R | 15kΩ 1/16W J | |
| R3213 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R3214 | NRSA63J-152X | MG R | 1.5kΩ 1/16W J | |
| R3215 | NRSA63J-680X | MG R | 68Ω 1/16W J | |
| R3216 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| △ R3217 | QRJ146J-100X | UNF R | 10Ω 1/4W J | |
| | | | | |
| R3221 | NRSA63J-470X | MG R | 47Ω 1/16W J | |
| R3222 | NRSA63J-470X | MG R | 47Ω 1/16W J | |
| R3224 | NRSA63J-122X | MG R | 1.2kΩ 1/16W J | |
| R3225 | QRE121J-563Y | C R | 56kΩ 1/2W J | |
| R3226 | QRE121J-563Y | C R | 56kΩ 1/2W J | |
| R3227 | NRSA63J-122X | MG R | 1.2kΩ 1/16W J | |
| R3228 | NRSA63J-390X | MG R | 39Ω 1/16W J | |
| R3229 | QRE121J-2R7Y | C R | 2.7Ω 1/2W J | |
| | | | | |
| R3230 | QRE121J-2R7Y | C R | 2.7Ω 1/2W J | |
| R3231 | NRSA63J-390X | MG R | 39Ω 1/16W J | |
| R3232 | QRE121J-121Y | C R | 120Ω 1/2W J | |
| R3233 | QRL029J-391 | OM R | 390Ω 2W J | |
| R3251 | NDC31HJ-331X | C CAP. | 330pF 50V J | |
| R3252 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R3253 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3254 | NRSA63J-563X | MG R | 56kΩ 1/16W J | |
| | | | | |
| R3255 | NRSA63J-223X | MG R | 22kΩ 1/16W J | |
| R3256 | NRSA63J-681X | MG R | 680Ω 1/16W J | |
| R3257 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3258 | NRSA63J-182X | MG R | 1.8kΩ 1/16W J | |
| R3259 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3260 | NRSA63J-271X | MG R | 270Ω 1/16W J | |
| R3261 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3262 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | | | | |
| R3263 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R3264 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R3265 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3266 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R3267 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3268 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R3269 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3270 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | | | | |
| R3271 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3272 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R3273 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R3274 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R3275 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|------------------|--------------|-------------|----------------|-------|
| CAPACITOR | | | | |
| C3101 | QETN1CM-477Z | E CAP. | 470μF 16V M | |
| C3107 | QETM2EM-106 | E CAP. | 10μF 250V M | |
| C3108 | QETM2EM-476 | E CAP. | 47μF 250V M | |
| C3110 | QCZ0131-222 | C CAP. | 2200pF 2000V K | |
| C3114 | QCS31HJ-151Z | C CAP. | 150pF 50V J | |
| C3115 | QETN1CM-476Z | E CAP. | 47μF 16V M | |
| C3116 | NDC31HJ-561X | C CAP. | 560pF 50V J | |
| C3117 | NCB31HK-471X | C CAP. | 470pF 50V K | |
| | | | | |
| C3118 | NCB31HK-471X | C CAP. | 470pF 50V K | |
| C3119 | QFLC1HJ-104Z | M CAP. | 0.1μF 50V J | |
| C3120 | QETN1HM-105Z | E CAP. | 1μF 50V M | |
| C3121 | NCB31HK-102X | C CAP. | 1000pF 50V K | |
| C3204 | NDC31HJ-561X | C CAP. | 560pF 50V J | |
| C3205 | QETN1HM-335Z | E CAP. | 3.3μF 50V M | |
| C3206 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C3207 | QCS31HJ-5R0Z | C CAP. | 5pF 50V J | |
| | | | | |
| C3209 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C3211 | NDC31HJ-391X | C CAP. | 390pF 50V J | |
| C3212 | QCB32HK-472Z | C CAP. | 4700pF 500V K | |
| C3213 | NDC31HJ-561X | C CAP. | 560pF 50V J | |
| C3214 | QETN2CM-106Z | E CAP. | 10μF 160V M | |
| C3215 | QCB32HK-472Z | C CAP. | 4700pF 500V K | |
| C3216 | QETN2CM-106Z | E CAP. | 10μF 160V M | |
| C3217 | QETN1AM-107Z | E CAP. | 100μF 10V M | |
| | | | | |
| C3218 | QETN1AM-107Z | E CAP. | 100μF 10V M | |
| C3219 | QETN1AM-337Z | E CAP. | 330μF 10V M | |
| C3220 | QCS32HJ-680Z | C CAP. | 68pF 500V J | |
| C3251 | QENC1HM-105Z | BP E CAP. | 1μF 50V M | |
| C3252 | NDC31HJ-151X | C CAP. | 150pF 50V J | |
| C3253 | NDC31HJ-560X | C CAP. | 56pF 50V J | |
| C3255 | NCB31HK-104X | C CAP. | 0.1μF 50V K | |
| C3261 | NDC31HJ-820X | C CAP. | 82pF 50V J | |
| | | | | |
| C3262 | NDC31HJ-820X | C CAP. | 82pF 50V J | |
| C3263 | NDC31HJ-820X | C CAP. | 82pF 50V J | |
| C3264 | QETN1AM-107Z | E CAP. | 100μF 10V M | |
| C3265 | QETN1AM-107Z | E CAP. | 100μF 10V M | |
| C3266 | QETN1AM-107Z | E CAP. | 100μF 10V M | |
| C3267 | QETN1CM-227Z | E CAP. | 220μF 16V M | |
| COIL | | | | |
| L3121 | QQL244J-5R6Z | COIL | 5.6μH J | |
| L3122 | QQLZ034-220 | COIL | 22μH | |
| L3251 | QQL244K-150Z | COIL | 15μH K | |
| DIODE | | | | |
| D3107 | MA111-X | SI. DIODE | | |
| D3108 | MA3075/H/-X | ZENER DIODE | | |
| D3109 | MA3051/H/-X | ZENER DIODE | | |
| D3110 | MA111-X | SI. DIODE | | |
| D3111 | MA3051/H/-X | ZENER DIODE | | |
| D3112 | MA111-X | SI. DIODE | | |
| D3113 | MA3051/H/-X | ZENER DIODE | | |
| D3114 | MA111-X | SI. DIODE | | |
| | | | | |
| D3118 | 1SS244-T2 | SI. DIODE | | |
| D3119 | 1SS244-T2 | SI. DIODE | | |
| D3120 | 1SS244-T2 | SI. DIODE | | |
| D3121 | 1SS244-T2 | SI. DIODE | | |
| D3122 | 1SS244-T2 | SI. DIODE | | |
| D3123 | 1SS244-T2 | SI. DIODE | | |
| D3124 | 1N4003-T2 | SI. DIODE | | |
| D3125 | 1N4003-T2 | SI. DIODE | | |
| | | | | |
| D3126 | 1N4003-T2 | SI. DIODE | | |
| D3127 | MA111-X | SI. DIODE | | |
| D3130 | MA3150/M/-X | ZENER DIODE | | |
| D3132 | MA3043-X | ZENER DIODE | | |
| D3132 | MA3043-X | ZENER DIODE | | |
| D3134 | 1SS244-T2 | SI. DIODE | | |
| D3136 | MA111-X | SI. DIODE | | |
| D3138 | MA111-X | SI. DIODE | | |

FRONT CONTROL PW BOARD ASS'Y (SCH-8004A-H2)

| △ Symbol No. | Part No. | Part Name | Description | Local |
|-------------------|-----------------|-----------------|--------------|-------|
| DIODE | | | | |
| D3141 | MTZJ30A-T2 | ZENER DIODE | | |
| D3142 | MTZJ30A-T2 | ZENER DIODE | | |
| D3143 | MTZJ30A-T2 | ZENER DIODE | | |
| D3201 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| D3202 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| D3203 | RGP10J-5025-T3 | SI. DIODE | | |
| D3204 | RGP10J-5025-T3 | SI. DIODE | | |
| TRANSISTOR | | | | |
| Q3101 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3102 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3103 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3104 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3105 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3106 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3121 | 2SC1740S/QR/-T | TRANSISTOR | | |
| Q3122 | 2SA933AS/QR/-T | TRANSISTOR | | |
| Q3123 | 2SC4075/DE/YA11 | POW TRANSISTOR | | |
| Q3124 | 2SC1740S/QR/-T | TRANSISTOR | | |
| Q3125 | 2SC4075/DE/YA11 | POW TRANSISTOR | | |
| Q3126 | 2SC1740S/QR/-T | TRANSISTOR | | |
| Q3127 | 2SC4075/DE/YA11 | POW TRANSISTOR | | |
| Q3128 | 2SC1740S/QR/-T | TRANSISTOR | | |
| Q3129 | 2SC3334-T | TRANSISTOR | | |
| Q3130 | 2SA1321-T | TRANSISTOR | | |
| Q3131 | 2SC3334-T | TRANSISTOR | | |
| Q3132 | 2SA1321-T | TRANSISTOR | | |
| Q3133 | 2SC3334-T | TRANSISTOR | | |
| Q3134 | 2SA1321-T | TRANSISTOR | | |
| Q3135 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q3204 | 2SC1740S/QR/-T | TRANSISTOR | | |
| Q3205 | 2SC1740S/QR/-T | TRANSISTOR | | |
| Q3206 | 2SA933AS/QR/-T | TRANSISTOR | | |
| Q3209 | 2SA1837 | POWER TRANSISTO | | |
| Q3210 | 2SC4793 | POWER TRANSISTO | | |
| Q3251 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q3252 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3253 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q3261 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q3262 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q3263 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q3264 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3265 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q3266 | 2SD601A/QR/-X | TRANSISTOR | | |
| OTHERS | | | | |
| CL3001 | QZW0027-004 | WIRE CLAMP | | |
| DL3261 | CE41925-001 | DELAY LINE | | |
| DL3262 | CE41925-001 | DELAY LINE | | |
| DL3263 | CE41925-001 | DELAY LINE | | |
| △ FR3201 | QRZ9021-561 | F R | 560Ω 1W J | |
| K3201 | CE41492-001Z | CHOKE COIL | | |
| K3202 | CE41492-001Z | CHOKE COIL | | |
| K3203 | CE41492-001Z | CHOKE COIL | | |
| K3204 | CE41492-001Z | CHOKE COIL | | |
| K3205 | QQR1113-001Z | FERRITE BEADS | | |
| K3206 | QQR1113-001Z | FERRITE BEADS | | |
| K3207 | QQR1113-001Z | FERRITE BEADS | | |
| K3208 | QQR1113-001Z | FERRITE BEADS | | |
| SG3101 | QAF0056-501Z | SURGE ABSORBER | | |
| SG3102 | QAF0056-501Z | SURGE ABSORBER | | |
| △ SK3001 | CE42670-001 | CRT SOCKET | | |
| W3034 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|-------------------|-----------------|-----------------|---------------|-------|
| RESISTOR | | | | |
| R8482 | NRSA63J-124X | MG R | 120kΩ 1/16W J | |
| R8483 | NRSA63J-683X | MG R | 68kΩ 1/16W J | |
| R8484 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | |
| R8485 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | |
| R8486 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| R8487 | NRSA63J-332X | MG R | 3.3kΩ 1/16W J | |
| R8488 | NRSA63J-154X | MG R | 150kΩ 1/16W J | |
| R8489 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R8491 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R8492 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R8495 | NRSA63J-152X | MG R | 1.5kΩ 1/16W J | |
| R8497 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | |
| R8499 | QRE121J-561Y | C R | 560Ω 1/2W J | |
| R8801 | NRSA63J-332X | MG R | 3.3kΩ 1/16W J | |
| R8802 | NRSA63J-392X | MG R | 3.9kΩ 1/16W J | |
| R8803 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | |
| R8805 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | |
| R8807 | NRSA63J-181X | MG R | 180Ω 1/16W J | |
| R8808 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R8809 | NRSA63J-331X | MG R | 330Ω 1/16W J | |
| R8810 | NRSA63J-471X | MG R | 470Ω 1/16W J | |
| R8811 | NRSA63J-821X | MG R | 820Ω 1/16W J | |
| R8812 | NRSA63J-122X | MG R | 1.2kΩ 1/16W J | |
| R8813 | NRSA63J-471X | MG R | 470Ω 1/16W J | |
| R8815 | QRE121J-271Y | C R | 270Ω 1/2W J | |
| R8816 | QRE121J-271Y | C R | 270Ω 1/2W J | |
| R8817 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R8818 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R8819 | NRSA63J-272X | MG R | 2.7kΩ 1/16W J | |
| R8826 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R8830 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R8831 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| △ R8901 | QRZ0111-474 | C R | 470kΩ 1W K | |
| CAPACITOR | | | | |
| C8481 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C8482 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C8483 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C8484 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C8485 | QETN1EM-476Z | E CAP. | 47μF 25V M | |
| C8487 | QFLC1HJ-103Z | M CAP. | 0.01μF 50V J | |
| C8660 | QETM1VM-108 | E CAP. | 1000μF 35V M | |
| C8661 | QETM1VM-108 | E CAP. | 1000μF 35V M | |
| C8801 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C8802 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C8803 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C8815 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| △ C8901 | QFZ9072-224 | MM CAP. | 0.22μF | |
| COIL | | | | |
| L8401 | QQL244K-820Z | COIL | 82μH K | |
| DIODE | | | | |
| D8801 | MA111-X | SI. DIODE | | |
| D8802 | P1241-04 | PHOTO CONDUCTOR | | |
| D8803 | SLR-342VR-T16 | LED | | |
| TRANSISTOR | | | | |
| Q8481 | 2SC2412K/QR/-X | TRANSISTOR | | |
| Q8801 | 2SA1037AK/QR/-X | TRANSISTOR | | |
| IC | | | | |
| IC8481 | LA6515 | I.C(MONO-ANA) | | |
| IC8801 | GP1UM281QK | IR DETECT UNIT | | |

| △ | Symbol No. | Part No. | Part Name | Description | Local |
|--------|------------|---------------|-------------|--------------|-------|
| OTHERS | | | | | |
| | | CM35921-005-H | CDS HOLDER | | |
| | | CM36626-B01-H | LED HOLDER | | |
| △ | F8901 | QMF51E2-4R0J4 | FUSE | | |
| | FC8901 | CEMG002-001Z | FUSE CLIP | | |
| | J8302 | QNN0279-003 | PIN JACK | | |
| | J8303 | QNN0279-002 | PIN JACK | | |
| | J8304 | QNN0279-001 | PIN JACK | | |
| | J8801 | QNS0155-001 | 3.5 JACK | | |
| △ | LF8901 | QQR1356-001 | LINE FILTER | | |
| | S8801 | QSW0619-003Z | TACT SWITCH | MENU | |
| | S8802 | QSW0619-003Z | TACT SWITCH | CH- | |
| | S8803 | QSW0619-003Z | TACT SWITCH | CH+ | |
| | S8804 | QSW0619-003Z | TACT SWITCH | VOL- | |
| | S8805 | QSW0619-003Z | TACT SWITCH | VOL+ | |
| | S8806 | QSW0619-003Z | TACT SWITCH | TV/VIDEO | |
| △ | S8901 | QSW0750-001 | PUSH SWITCH | POWER | |
| △ | VA8901 | QAF0052-621 | VARISTOR | | |
| | Y8401 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |

REMOTE CONTROL UNIT PARTS LIST (RM-C1019-1H)

| △ | Ref.No | Part No. | Part Name | Description | Local |
|---|--------|----------|---------------|-------------|-------|
| | | 25-1168F | BATTERY COVER | | |

| △ | Symbol No. | Part No. | Part Name | Description | Local |
|---|------------|----------|-----------|-------------|-------|
|---|------------|----------|-----------|-------------|-------|

PRINTED WIRING BOARD PARTS LIST [AV-29W33B/PH] MAIN PW BOARD ASS'Y(SCH-1083A-H2)

| △ | Symbol No. | Part No. | Part Name | Description | Local | △ | Symbol No. | Part No. | Part Name | Description | Local |
|-----------------|------------|--------------|-----------|---------------|-------|-----------------|------------|---------------|-----------|---------------|-------|
| RESISTOR | | | | | | RESISTOR | | | | | |
| | R1001 | NRSA63J-221X | MG R | 220Ω 1/16W J | | △ | R1532 | QRZ9017-4R7 | F R | 4.7Ω 1/4W J | |
| | R1002 | NRSA63J-221X | MG R | 220Ω 1/16W J | | | R1541 | QRE121J-124Y | C R | 120kΩ 1/2W J | |
| | R1003 | NRSA63J-392X | MG R | 3.9kΩ 1/16W J | | | R1542 | QRE121J-124Y | C R | 120kΩ 1/2W J | |
| | R1004 | NRSA63J-221X | MG R | 220Ω 1/16W J | | | R1543 | QRE121J-471Y | C R | 470Ω 1/2W J | |
| | R1005 | NRSA63J-273X | MG R | 27kΩ 1/16W J | | | R1545 | QRE121J-220Y | C R | 22Ω 1/2W J | |
| | R1006 | NRSA63J-750X | MG R | 75Ω 1/16W J | | | R1546 | QRE121J-822Y | C R | 8.2kΩ 1/2W J | |
| | R1101 | NRSA63J-100X | MG R | 10Ω 1/16W J | | △ | R1547 | QRZ9011-4R7 | F R | 4.7Ω 1/2W J | |
| | R1102 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | | | R1561 | QRL029J-220 | OM R | 22Ω 2W J | |
| | R1103 | NRSA63J-272X | MG R | 2.7kΩ 1/16W J | | | R1562 | QRE121J-123Y | C R | 12kΩ 1/2W J | |
| | R1104 | NRSA63J-181X | MG R | 180Ω 1/16W J | | | R1563 | QRZ0056-103Z | COMP R | 10kΩ 1/2W K | |
| | R1105 | NRSA63J-220X | MG R | 22Ω 1/16W J | | | R1591 | QRA14CF-1202Y | CMF R | 12kΩ 1/4W F | |
| | R1106 | NRSA63J-101X | MG R | 100Ω 1/16W J | | | R1592 | QRZ0225-2R2 | UNF R | 2.2Ω 2W | |
| | R1107 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | | | R1593 | NRSA02F-332X | MG R | 3.3kΩ 1/10W F | |
| | R1108 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | | R1594 | QRE121J-183Y | C R | 18kΩ 1/2W J | |
| | R1109 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | | R1595 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| | R1110 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | | R1602 | NRSA63J-271X | MG R | 270Ω 1/16W J | |
| | R1113 | NRSA63J-102X | MG R | 1kΩ 1/16W J | | | R1603 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1114 | NRSA63J-102X | MG R | 1kΩ 1/16W J | | | R1604 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1115 | NRSA63J-471X | MG R | 470Ω 1/16W J | | | R1621 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| | R1150 | NRSA63J-331X | MG R | 330Ω 1/16W J | | | R1622 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| | R1151 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | | R1623 | NRSA63J-473X | MG R | 47kΩ 1/16W J | |
| | R1152 | NRSA63J-121X | MG R | 120Ω 1/16W J | | | R1624 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1153 | NRSA63J-122X | MG R | 1.2kΩ 1/16W J | | | R1625 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1154 | NRSA63J-181X | MG R | 180Ω 1/16W J | | | R1628 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1301 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | | R1629 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| | R1302 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | | R1630 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| | R1303 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | | R1650 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1304 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | | R1651 | NRSA63J-822X | MG R | 8.2kΩ 1/16W J | |
| | R1305 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | | | R1652 | NRSA63J-822X | MG R | 8.2kΩ 1/16W J | |
| | R1306 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | | R1653 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| | R1307 | NRSA63J-103X | MG R | 10kΩ 1/16W J | | | R1654 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1308 | NRSA63J-101X | MG R | 100Ω 1/16W J | | | R1655 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| | R1309 | NRSA63J-473X | MG R | 47kΩ 1/16W J | | | R1656 | QRE121J-2R2Y | C R | 2.2Ω 1/2W J | |
| | R1310 | NRSA63J-473X | MG R | 47kΩ 1/16W J | | | R1657 | QRE121J-2R2Y | C R | 2.2Ω 1/2W J | |
| | R1311 | NRSA63J-123X | MG R | 12kΩ 1/16W J | | | R1658 | NRSA63J-822X | MG R | 8.2kΩ 1/16W J | |
| | R1317 | QRL029J-101 | OM R | 100Ω 2W J | | | R1659 | NRSA63J-822X | MG R | 8.2kΩ 1/16W J | |
| | R1401 | NRSA63J-123X | MG R | 12kΩ 1/16W J | | | R1660 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1403 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | | | R1661 | NRSA63J-683X | MG R | 68kΩ 1/16W J | |
| | R1405 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | | | R1662 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| | R1406 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | | | R1663 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1408 | NRSA63J-682X | MG R | 6.8kΩ 1/16W J | | | R1664 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| | R1410 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | | | R1666 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1411 | QRG01GJ-221 | OM R | 220Ω 1W J | | | R1667 | NRSA63J-392X | MG R | 3.9kΩ 1/16W J | |
| | R1412 | QRE121J-1R0Y | C R | 1Ω 1/2W J | | | R1668 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| | R1413 | QRX01GJ-1R2 | MF R | 1.2Ω 1W J | | | R1669 | NRSA63J-822X | MG R | 8.2kΩ 1/16W J | |
| | R1414 | QRE121J-2R2Y | C R | 2.2Ω 1/2W J | | | R1688 | NRSA63J-273X | MG R | 27kΩ 1/16W J | |
| | R1425 | NRSA63J-153X | MG R | 15kΩ 1/16W J | | | R1690 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| | R1478 | NRSA63J-101X | MG R | 100Ω 1/16W J | | | R1691 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| | R1479 | NRSA63J-101X | MG R | 100Ω 1/16W J | | | R1695 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1480 | QRE121J-681Y | C R | 680Ω 1/2W J | | | R1696 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| | R1481 | NRSA63J-223X | MG R | 22kΩ 1/16W J | | | R1701 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1482 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | | R1702 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1483 | NRSA63J-823X | MG R | 82kΩ 1/16W J | | | R1703 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1484 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | | R1704 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| | R1485 | NRSA63J-123X | MG R | 12kΩ 1/16W J | | | R1706 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| | R1486 | NRSA63J-272X | MG R | 2.7kΩ 1/16W J | | | R1707 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| | R1487 | NRSA63J-333X | MG R | 33kΩ 1/16W J | | | R1708 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| | R1489 | NRSA63J-122X | MG R | 1.2kΩ 1/16W J | | | R1709 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| | R1490 | NRSA63J-102X | MG R | 1kΩ 1/16W J | | | R1710 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| | R1491 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | | | R1711 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1492 | NRSA63J-822X | MG R | 8.2kΩ 1/16W J | | | R1712 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1493 | QRE121J-223Y | C R | 22kΩ 1/2W J | | | R1713 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1494 | QRL039J-330 | OM R | 33Ω 3W J | | | R1714 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1521 | NRSA63J-101X | MG R | 100Ω 1/16W J | | | R1715 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | R1522 | NRSA63J-102X | MG R | 1kΩ 1/16W J | | | R1716 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1523 | QRL039J-151 | OM R | 150Ω 3W J | | | R1717 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | R1524 | QRL039J-151 | OM R | 150Ω 3W J | | | R1718 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| | R1526 | QRL029J-271 | OM R | 270Ω 2W J | | | R1719 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| | R1527 | QRL039J-103 | OM R | 10kΩ 3W J | | | R1720 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| △ | R1528 | QRZ9021-1R0 | F R | 1Ω 1W J | | | R1721 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| △ | R1529 | QRZ9021-1R0 | F R | 1Ω 1W J | | | R1722 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| | R1531 | NRSA63J-182X | MG R | 1.8kΩ 1/16W J | | | R1723 | NRSA63J-221X | MG R | 220Ω 1/16W J | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|-----------------|--------------|-----------|---------------|-------|
| RESISTOR | | | | |
| R1724 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1725 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1726 | NRSA63J-472X | MG R | 4.7kΩ 1/16W J | |
| R1727 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R1728 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1730 | NRSA63J-223X | MG R | 22kΩ 1/16W J | |
| R1731 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1732 | NRSA02F-393X | MG R | 39kΩ 1/10W F | |
| | | | | |
| R1733 | NRSA63J-273X | MG R | 27kΩ 1/16W J | |
| R1734 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| R1735 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| R1736 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| R1737 | NRSA63J-272X | MG R | 2.7kΩ 1/16W J | |
| R1738 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1739 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1740 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | | | | |
| R1741 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1742 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1744 | NRSA63J-561X | MG R | 560Ω 1/16W J | |
| R1745 | NRSA63J-105X | MG R | 1MΩ 1/16W J | |
| R1746 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| R1747 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1748 | NRSA02J-225X | MG R | 2.2MΩ 1/10W J | |
| R1749 | NRSA02J-185X | MG R | 1.8MΩ 1/10W J | |
| | | | | |
| R1750 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1755 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1756 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1757 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1758 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1790 | NRSA63J-270X | MG R | 27Ω 1/16W J | |
| R1803 | NRSA63J-333X | MG R | 33kΩ 1/16W J | |
| R1804 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| | | | | |
| R1805 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1806 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1807 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1808 | NRSA63J-823X | MG R | 82kΩ 1/16W J | |
| R1809 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| R1810 | NRSA63J-823X | MG R | 82kΩ 1/16W J | |
| R1811 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| R1812 | NRSA63J-104X | MG R | 100kΩ 1/16W J | |
| | | | | |
| R1813 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1815 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1818 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1820 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1821 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1823 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1824 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1826 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| | | | | |
| R1829 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| R1830 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1831 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1832 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| R1833 | NRSA63J-271X | MG R | 270Ω 1/16W J | |
| R1834 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | |
| R1835 | NRSA63J-562X | MG R | 5.6kΩ 1/16W J | |
| R1836 | NRSA63J-750X | MG R | 75Ω 1/16W J | |
| | | | | |
| R1837 | NRSA63J-101X | MG R | 100Ω 1/16W J | |
| R1838 | QRK126J-121X | UNF R | 120Ω 1/2W J | |
| R1839 | QRE121J-221Y | C R | 220Ω 1/2W J | |
| R1840 | QRE121J-221Y | C R | 220Ω 1/2W J | |
| R1841 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1842 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1843 | NRSA63J-821X | MG R | 820Ω 1/16W J | |
| R1844 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| | | | | |
| R1845 | NRSA63J-102X | MG R | 1kΩ 1/16W J | |
| R1846 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| R1847 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1848 | NRSA63J-221X | MG R | 220Ω 1/16W J | |
| R1849 | NRSA63J-471X | MG R | 470Ω 1/16W J | |
| R1850 | QRE141J-0R0Y | C R | 0.0Ω 1/4W J | |
| R1880 | NRSA63J-202X | MG R | 2kΩ 1/16W J | |
| R1881 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|------------------|--------------|-----------|----------------|-------|
| RESISTOR | | | | |
| R1882 | NRSA63J-181X | MG R | 180Ω 1/16W J | |
| R1883 | NRSA63J-471X | MG R | 470Ω 1/16W J | |
| R1902 | QRF154K-2R2 | UNF R | 2.2Ω 15W K | |
| R1903 | QRL039J-393 | OM R | 39kΩ 3W J | |
| R1904 | QRE121J-221Y | C R | 220Ω 1/2W J | |
| R1905 | QRM034J-R10 | MP R | 0.1Ω 3W J | |
| R1906 | QRE141J-1R5Y | C R | 1.5Ω 1/4W J | |
| R1908 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| | | | | |
| R1911 | QRE121J-152Y | C R | 1.5kΩ 1/2W J | |
| R1912 | QRE121J-123Y | C R | 12kΩ 1/2W J | |
| △ R1913 | QRZ9017-100 | F R | 10Ω 1/4W J | |
| R1914 | QRL039J-473 | OM R | 47kΩ 3W J | |
| R1915 | NRSA63J-823X | MG R | 82kΩ 1/16W J | |
| R1916 | NRSA63J-154X | MG R | 150kΩ 1/16W J | |
| R1951 | QRE121J-223Y | C R | 22kΩ 1/2W J | |
| R1952 | NRSA63J-222X | MG R | 2.2kΩ 1/16W J | |
| | | | | |
| R1953 | QRE121J-152Y | C R | 1.5kΩ 1/2W J | |
| R1954 | QRE121J-150Y | C R | 15Ω 1/2W J | |
| R1955 | QRG01GJ-330 | OM R | 33Ω 1W J | |
| R1956 | QRE121J-120Y | C R | 12Ω 1/2W J | |
| R1957 | QRE121J-5R6Y | C R | 5.6Ω 1/2W J | |
| R1958 | QRL039J-820 | OM R | 82Ω 3W J | |
| R1959 | QRE121J-820Y | C R | 82Ω 1/2W J | |
| R1960 | NRSA63J-391X | MG R | 390Ω 1/16W J | |
| | | | | |
| R1961 | QRL029J-223 | OM R | 22kΩ 2W J | |
| R1962 | NRSA63J-681X | MG R | 680Ω 1/16W J | |
| R1963 | QRE121J-332Y | C R | 3.3kΩ 1/2W J | |
| R1964 | NRSA63J-103X | MG R | 10kΩ 1/16W J | |
| R1965 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| R1966 | NRSA63J-223X | MG R | 22kΩ 1/16W J | |
| R1967 | NRSA63J-473X | MG R | 47kΩ 1/16W J | |
| R1968 | NRSA63J-331X | MG R | 330Ω 1/16W J | |
| | | | | |
| R1969 | QRT029J-R82 | MF R | 0.82Ω 2W J | |
| R1970 | NRSA63J-153X | MG R | 15kΩ 1/16W J | |
| R1971 | NRSA63J-183X | MG R | 18kΩ 1/16W J | |
| R1972 | QRE121J-182Y | C R | 1.8kΩ 1/2W J | |
| R1973 | QRE121J-332Y | C R | 3.3kΩ 1/2W J | |
| R1974 | QRT029J-R82 | MF R | 0.82Ω 2W J | |
| △ R1991 | QRZ0057-825 | C R | 8.2MΩ 1W J | |
| CAPACITOR | | | | |
| C1001 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1002 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1003 | QFV71HJ-104Z | MF CAP. | 0.1μF 50V J | |
| C1004 | QETN1CM-477Z | E CAP. | 470μF 16V M | |
| C1005 | NCB31HK-222X | C CAP. | 2200pF 50V K | |
| C1006 | QETN1CM-336Z | E CAP. | 33μF 16V M | |
| C1007 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1101 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| | | | | |
| C1102 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| C1103 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| C1104 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| C1106 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1107 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1109 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1150 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| C1151 | NCB31HK-472X | C CAP. | 4700pF 50V K | |
| | | | | |
| C1301 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1302 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1304 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1305 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1306 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1307 | NDC31HJ-330X | C CAP. | 33pF 50V J | |
| C1308 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1401 | QETN1HM-336Z | E CAP. | 33μF 50V M | |
| | | | | |
| C1402 | QCB31HK-682Z | C CAP. | 6800pF 50V K | |
| C1403 | QEHR1VM-107Z | E CAP. | 100μF 35V M | |
| C1406 | QFLC2AJ-683Z | M CAP. | 0.068μF 100V J | |
| C1407 | QCS32HJ-180Z | C CAP. | 18pF 500V J | |
| C1411 | NCF21HZ-334X | C CAP. | 0.33μF 50V Z | |
| C1412 | NCF21HZ-334X | C CAP. | 0.33μF 50V Z | |
| C1413 | QFLC2AJ-563Z | M CAP. | 0.056μF 100V J | |
| C1422 | QEHQ1VM-108 | E CAP. | 1000μF 35V M | |

| △ Symbol No. | Part No. | Part Name | Description | Local | △ Symbol No. | Part No. | Part Name | Description | Local |
|------------------|--------------|----------------|-------------------|-------|------------------|--------------|-----------|---------------|-------|
| CAPACITOR | | | | | CAPACITOR | | | | |
| C1471 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1654 | NCF21HZ-224X | C CAP. | 0.22μF 50V Z | |
| C1480 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1655 | NCF21HZ-224X | C CAP. | 0.22μF 50V Z | |
| C1483 | QEZO195-475Z | BP E CAPACITOR | 4.7μF 50V M | | C1656 | NCF21HZ-224X | C CAP. | 0.22μF 50V Z | |
| C1485 | QETN1HM-226Z | E CAP. | 22μF 50V M | | C1657 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1521 | QETN1VM-476Z | E CAP. | 47μF 35V M | | C1658 | QETN1VM-228 | E CAP. | 2200μF 35V M | |
| C1522 | QFLC1HJ-332Z | M CAP. | 3300pF 50V J | | C1662 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1523 | QFLC1HJ-223Z | M CAP. | 0.022μF 50V J | | C1681 | QETN1CM-227Z | E CAP. | 220μF 16V M | |
| C1524 | QFZO196-382 | MPP CAP. | 3800pF 1.5kVH±3% | | C1682 | QETN1CM-227Z | E CAP. | 220μF 16V M | |
| C1525 | QFZO200-143 | MPP CAP. | 0.014μF 1.5kVH±3% | | C1683 | QETN1CM-336Z | E CAP. | 33μF 16V M | |
| C1526 | QFP32JJ-223 | PP CAP. | 0.022μF 630V J | | C1684 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1527 | QFZO199-224 | MPP CAP. | 0.22μF AC250V J | | C1702 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1528 | QFZO199-224 | MPP CAP. | 0.22μF AC250V J | | C1703 | NDC31HJ-330X | C CAP. | 33pF 50V J | |
| C1529 | QENC2AM-225Z | BP E CAP. | 2.2μF 100V M | | C1704 | NDC31HJ-330X | C CAP. | 33pF 50V J | |
| C1530 | QCB32HK-561Z | C CAP. | 560pF 500V K | | C1706 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C1531 | QEHR1EM-108Z | E CAP. | 1000μF 25V M | | C1707 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1532 | QCB32HK-561Z | C CAP. | 560pF 500V K | | C1709 | QETN1CM-477Z | E CAP. | 470μF 16V M | |
| C1533 | QEHR1EM-108Z | E CAP. | 1000μF 25V M | | C1710 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C1534 | QCB32HK-561Z | C CAP. | 560pF 500V K | | C1711 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1536 | QFLC1HJ-103Z | M CAP. | 0.01μF 50V J | | C1712 | QETN1CM-476Z | E CAP. | 47μF 16V M | |
| C1540 | QFV71HJ-104Z | MF CAP. | 0.1μF 50V J | | C1713 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1541 | QETN2EM-106Z | E CAP. | 10μF 250V M | | C1720 | QETN1EM-476Z | E CAP. | 47μF 25V M | |
| C1550 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1725 | NCB31HK-681X | C CAP. | 680pF 50V K | |
| C1561 | QFV21HJ-154Z | MF CAP. | 0.15μF 50V J | | C1729 | QETN1CM-476Z | E CAP. | 47μF 16V M | |
| C1566 | QFZO200-113 | MPP CAP. | 0.011μF 1.5kVH±3% | | C1730 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C1591 | QETN1CM-107Z | E CAP. | 100μF 16V M | | C1731 | NCB21EK-224X | C CAP. | 0.22μF 25V K | |
| C1592 | QETM2CM-227 | E CAP. | 220μF 160V M | | C1732 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1593 | QETN1EM-476Z | E CAP. | 47μF 25V M | | C1733 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1602 | NCB31HK-103X | C CAP. | 0.01μF 50V K | | C1734 | NCB31HK-222X | C CAP. | 2200pF 50V K | |
| C1603 | QETN1CM-107Z | E CAP. | 100μF 16V M | | C1735 | NCB31HK-222X | C CAP. | 2200pF 50V K | |
| C1604 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1736 | QETN1HM-105Z | E CAP. | 1μF 50V M | |
| C1606 | NDC31HJ-2R0X | C CAP. | 2.0pF 50V J | | C1737 | QETN1HM-105Z | E CAP. | 1μF 50V M | |
| C1607 | NDC31HJ-2R0X | C CAP. | 2.0pF 50V J | | C1738 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1608 | NCB31HK-103X | C CAP. | 0.01μF 50V K | | C1739 | NFV41CJ-104X | MPP CAP. | 0.1μF 16V J | |
| C1609 | NCB31HK-103X | C CAP. | 0.01μF 50V K | | C1740 | QETN1HM-225Z | E CAP. | 2.2μF 50V M | |
| C1610 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1741 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1611 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1742 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1612 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1743 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1613 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1744 | NCB31HK-222X | C CAP. | 2200pF 50V K | |
| C1615 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1745 | NCB31HK-473X | CH C CAP. | 0.047μF 50V K | |
| C1616 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1747 | NCB31HK-473X | CH C CAP. | 0.047μF 50V K | |
| C1617 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1749 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1618 | NCB31CK-104X | C CAP. | 0.1μF 16V K | | C1751 | NCB21HK-104X | C CAP. | 0.1μF 50V K | |
| C1619 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1752 | NCB21HK-104X | C CAP. | 0.1μF 50V K | |
| C1620 | NCB31HK-102X | C CAP. | 1000pF 50V K | | C1753 | NCB21HK-104X | C CAP. | 0.1μF 50V K | |
| C1621 | NCB31HK-102X | C CAP. | 1000pF 50V K | | C1801 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1625 | NCF21EZ-474X | C CAP. | 0.47μF 25V Z | | C1802 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1626 | NCB31HK-333X | CH C CAP. | 0.033μF 50V K | | C1803 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1627 | NCB31HK-473X | CH C CAP. | 0.047μF 50V K | | C1804 | QETN1HM-106Z | E CAP. | 10μF 50V M | |
| C1628 | NCB21HK-823X | C CAP. | 0.082μF 50V K | | C1805 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1629 | NCB31HK-222X | C CAP. | 2200pF 50V K | | C1807 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1630 | NCB31HK-104X | C CAP. | 0.1μF 50V K | | C1808 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1631 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1810 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1632 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1811 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1633 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1812 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1634 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1813 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1635 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1814 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1636 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1815 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1637 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1817 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1638 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1819 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1639 | QETN1HM-107Z | E CAP. | 100μF 50V M | | C1820 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1640 | NCF21HZ-334X | C CAP. | 0.33μF 50V Z | | C1821 | NCF31AZ-105X | C CAP. | 1μF 10V Z | |
| C1641 | QETN1HM-475Z | E CAP. | 4.7μF 50V M | | C1822 | QETN1CM-477Z | E CAP. | 470μF 16V M | |
| C1642 | QETN1HM-106Z | E CAP. | 10μF 50V M | | C1823 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1643 | NCB31HK-104X | C CAP. | 0.1μF 50V K | | C1824 | QETN1CM-107Z | E CAP. | 100μF 16V M | |
| C1644 | NCB31HK-222X | C CAP. | 2200pF 50V K | | C1825 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1645 | NCB31HK-104X | C CAP. | 0.1μF 50V K | | C1826 | NCB31CK-104X | C CAP. | 0.1μF 16V K | |
| C1646 | NCB31HK-104X | C CAP. | 0.1μF 50V K | | C1827 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1647 | NCF21EZ-474X | C CAP. | 0.47μF 25V Z | | C1829 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1650 | NCF31AZ-105X | C CAP. | 1μF 10V Z | | C1830 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1651 | QEHR1HM-107Z | E CAP. | 100μF 50V M | | C1831 | NCB31HK-103X | C CAP. | 0.01μF 50V K | |
| C1652 | QETN1HM-105Z | E CAP. | 1μF 50V M | | C1833 | QETN1HM-226Z | E CAP. | 22μF 50V M | |
| C1653 | NCF21HZ-224X | C CAP. | 0.22μF 50V Z | | C1834 | NDC31HJ-181X | C CAP. | 180pF 50V J | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|------------------|--------------|-----------|---------------|-------|
| CAPACITOR | | | | |
| △ C1902 | QFZ9072-104 | MM CAP. | 0.1μF | |
| C1903 | QCZ9015-102Z | C CAP. | 1000pF AC250V | Z |
| C1904 | QCZ9015-102Z | C CAP. | 1000pF AC250V | Z |
| C1905 | QCZ9015-102Z | C CAP. | 1000pF AC250V | Z |
| C1907 | QEZ0371-337 | E CAP. | 330μF 400V | M |
| C1909 | QCZ0325-102 | C CAP. | 1000pF 2000V | K |
| C1910 | NDC31HJ-102X | C CAP. | 1000pF 50V | J |
| C1911 | QETN1VM-107Z | E CAP. | 100μF 35V | M |
| C1913 | QFLC1HJ-638Z | M CAP. | 6300μF 50V | J |
| C1915 | QCB32HK-222Z | C CAP. | 2200pF 500V | K |
| C1916 | QETN1HM-475Z | E CAP. | 4.7μF 50V | M |
| C1917 | QCB32HK-181Z | C CAP. | 180pF 500V | K |
| C1918 | QCB32HK-103 | C CAP. | 0.01μF 500V | K |
| C1919 | QCZ0325-391 | C CAP. | 390pF 2000V | K |
| C1920 | QCZ0122-471 | C CAP. | 470pF 2000V | K |
| C1921 | QFN31HJ-473Z | M CAP. | 0.047μF 50V | J |
| C1922 | QETN2AM-226Z | E CAP. | 22μF 100V | M |
| C1952 | QCB32HK-471Z | C CAP. | 470pF 500V | K |
| C1953 | QEHQ1VM-228 | E CAP. | 2200μF 35V | M |
| C1955 | QCB32HK-471Z | C CAP. | 470pF 500V | K |
| C1956 | QETN1VM-107Z | E CAP. | 100μF 35V | M |
| C1957 | QCB31HK-471Z | C CAP. | 470pF 50V | K |
| C1958 | QEHR1CM-108Z | E CAP. | 1000μF 16V | M |
| C1959 | QCZ0364-561 | C CAP. | 560pF | |
| C1960 | QEZ0203-227 | E CAP. | 220μF 160V | M |
| C1961 | QETN1CM-476Z | E CAP. | 47μF 16V | M |
| C1962 | QETN1HM-106Z | E CAP. | 10μF 50V | M |
| C1963 | QETN1CM-477Z | E CAP. | 470μF 16V | M |
| C1964 | QETN1EM-476Z | E CAP. | 47μF 25V | M |
| C1965 | QETN1VM-476Z | E CAP. | 47μF 35V | M |
| C1966 | QETN1CM-107Z | E CAP. | 100μF 16V | M |
| C1968 | NCB31CK-104X | C CAP. | 0.1μF 16V | K |
| C1970 | QETN1CM-107Z | E CAP. | 100μF 16V | M |
| C1972 | QETN1EM-476Z | E CAP. | 47μF 25V | M |
| C1974 | NCB31CK-104X | C CAP. | 0.1μF 16V | K |
| C1975 | QETN1CM-227Z | E CAP. | 220μF 16V | M |
| C1977 | QETN1EM-476Z | E CAP. | 47μF 25V | M |
| C1978 | NCB21HK-104X | C CAP. | 0.1μF 50V | K |
| C1980 | QETN1CM-107Z | E CAP. | 100μF 16V | M |
| C1981 | NCB31HK-102X | C CAP. | 1000pF 50V | K |
| C1982 | QETN1CM-476Z | E CAP. | 47μF 16V | M |
| C1983 | QETN1CM-227Z | E CAP. | 220μF 16V | M |
| △ C1991 | QCZ9079-102 | C CAP. | 1000pF AC250V | M |
| △ C1992 | QCZ9079-102 | C CAP. | 1000pF AC250V | M |
| △ C1993 | QCZ9079-102 | C CAP. | 1000pF AC250V | M |

TRANSFORMER

| | | |
|---------|-------------|------------------|
| T1521 | QQR1229-001 | DRIVE TRANSF |
| △ T1551 | QQH0139-001 | FBT(HV WIRELESS) |
| T1561 | QQR1153-001 | DEF TRANSF |
| △ T1901 | QQS0177-001 | SW TRANSF |

COIL

| | | | | |
|-------|--------------|----------------|----------|---|
| L1001 | QQL244K-8R2Z | COIL | 8.2μH | K |
| L1002 | QQL244K-8R2Z | COIL | 8.2μH | K |
| L1101 | QQL244J-5R6Z | COIL | 5.6μH | J |
| L1102 | QQL244K-180Z | COIL | 18μH | K |
| L1301 | QQL244K-221Z | PEAKING COIL | 220μH | K |
| L1401 | QQL26AK-220Z | COIL | 22μH | K |
| L1480 | QQR1138-001 | CHOKE COIL | | |
| L1523 | QQR1243-001 | LINEARITY COIL | | |
| L1541 | QQL244K-220Z | COIL | 22μH | K |
| L1561 | QQLZ028-272 | COIL | 2.7NANOH | |
| L1601 | QQL244K-4R7Z | COIL | 4.7μH | K |
| L1701 | QQL244K-100Z | COIL | 10μH | K |
| L1702 | QQL244K-100Z | COIL | 10μH | K |
| L1731 | QQL244J-101Z | COIL | 100μH | J |
| L1951 | QQLZ034-460 | COIL | 46μH | K |
| L1953 | QQL244J-5R6Z | COIL | 5.6μH | J |
| L1954 | QQL26AK-820Z | COIL | 82μH | K |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|--------------|----------------|--------------|-------------|-------|
| DIODE | | | | |
| D1101 | DAN235K-X | SI. DIODE | | |
| D1301 | MTZJ5.1B-T2 | ZENER DIODE | | |
| D1401 | RGP10J-5025-T3 | SI. DIODE | | |
| D1402 | MTZJ75-T2 | ZENER DIODE | | |
| D1405 | 1N4003-T2 | SI. DIODE | | |
| D1408 | MA111-X | SI. DIODE | | |
| D1480 | MTZJ4.3A-T2 | ZENER DIODE | | |
| D1521 | RH3G-F1 | SI. DIODE | | |
| D1522 | 31DF6N-FC5 | SI. DIODE | | |
| D1523 | RGP10J-5025-T3 | SI. DIODE | | |
| D1541 | RGP10J-5025-T3 | SI. DIODE | | |
| D1550 | MA111-X | SI. DIODE | | |
| D1551 | EU2-T3 | SI. DIODE | | |
| D1553 | RGP10J-5025-T3 | SI. DIODE | | |
| D1554 | RGP10J-5025-T3 | SI. DIODE | | |
| D1592 | MA3075/H-X | ZENER DIODE | | |
| D1651 | MA3330/L-X | ZENER DIODE | | |
| D1652 | MA3330/L-X | ZENER DIODE | | |
| D1653 | MA3330/L-X | ZENER DIODE | | |
| D1655 | MA111-X | SI. DIODE | | |
| D1656 | MA111-X | SI. DIODE | | |
| D1657 | MA111-X | SI. DIODE | | |
| D1701 | MA111-X | SI. DIODE | | |
| D1702 | MA3020-X | ZENER DIODE | | |
| D1703 | MA3036-X | ZENER DIODE | | |
| D1730 | MA111-X | SI. DIODE | | |
| D1731 | MA111-X | SI. DIODE | | |
| D1732 | MA111-X | SI. DIODE | | |
| D1733 | MA111-X | SI. DIODE | | |
| D1801 | MA3120/M-X | ZENER DIODE | | |
| D1802 | MA3120/M-X | ZENER DIODE | | |
| D1901 | GSIB460 | BRIDGE DIODE | | |
| D1902 | MTZJ33B-T2 | ZENER DIODE | | |
| D1906 | MTZJ27B-T2 | ZENER DIODE | | |
| D1907 | MTZJ33B-T2 | ZENER DIODE | | |
| D1908 | MA3200/M-X | ZENER DIODE | | |
| D1909 | 1SS133-T2 | SI. DIODE | | |
| D1911 | RGP10J-5025-T3 | SI. DIODE | | |
| D1912 | RGP10J-5025-T3 | SI. DIODE | | |
| D1913 | RGP10M-5010-T3 | SI. DIODE | | |
| D1914 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W | J |
| D1915 | MTZJ39B-T2 | ZENER DIODE | | |
| D1916 | MTZJ15B-T2 | ZENER DIODE | | |
| D1917 | 1SS133-T2 | SI. DIODE | | |
| D1919 | 1SS133-T2 | SI. DIODE | | |
| D1920 | MTZJ15B-T2 | ZENER DIODE | | |
| D1950 | RGP10J-5025-T3 | SI. DIODE | | |
| D1952 | FSF05A20 | SI. DIODE | | |
| D1953 | RGP10J-5025-T3 | SI. DIODE | | |
| D1954 | RU30A-F1 | SI. DIODE | | |
| D1955 | 1SR35-400A-T2 | SI. DIODE | | |
| D1956 | 31DF6N-FC5 | SI. DIODE | | |
| D1958 | MTZJ5.1A-T2 | ZENER DIODE | | |
| D1960 | MA111-X | SI. DIODE | | |
| D1964 | MA3330/L-X | ZENER DIODE | | |
| D1966 | MA3047/L-X | ZENER DIODE | | |
| D1968 | MA111-X | SI. DIODE | | |
| D1969 | MA111-X | SI. DIODE | | |
| D1970 | MTZJ9.1B-T2 | ZENER DIODE | | |
| D1971 | NRSA02J-0R0X | MG R | 0.0Ω 1/10W | J |

TRANSISTOR

| | | |
|-------|---------------|------------------|
| Q1101 | 2SC5083/L-P/T | TRANSISTOR |
| Q1106 | 2SB709A/QR/-X | TRANSISTOR |
| Q1108 | 2SD601A/QR/-X | TRANSISTOR |
| Q1150 | 2SD601A/QR/-X | TRANSISTOR |
| Q1301 | 2SB709A/QR/-X | TRANSISTOR |
| Q1302 | 2SB709A/QR/-X | TRANSISTOR |
| Q1303 | UN2212-X | DIGI. TRANSISTOR |
| Q1304 | 2SD601A/QR/-X | TRANSISTOR |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|-------------------|-----------------|------------------|-------------|-------|
| TRANSISTOR | | | | |
| Q1480 | 2SD1408/OY/-LB | POW TRANSISTOR | | |
| Q1521 | 2SC2655/Y/-T | TRANSISTOR | | |
| Q1522 | 2SD2634-YD | POW TRANSISTOR | | |
| Q1591 | 2SA1208/ST/Z1-T | TRANSISTOR | | |
| Q1592 | UN2212-X | DIGI. TRANSISTOR | | |
| Q1660 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1661 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1662 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1663 | UN2212-X | DIGI. TRANSISTOR | | |
| Q1683 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1684 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1685 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1686 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1701 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1702 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1720 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1801 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1802 | DTC323TK-X | DIGI. TRANSISTOR | | |
| Q1803 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1804 | 2SC1740S/QR/-T | TRANSISTOR | | |
| Q1860 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1861 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1862 | 2SB709A/QR/-X | TRANSISTOR | | |
| Q1901 | 2SC3852A | POW TRANSISTOR | | |
| Q1951 | 2SA1013/RO/-T | TRANSISTOR | | |
| Q1952 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1953 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1954 | 2SD601A/QR/-X | TRANSISTOR | | |
| Q1955 | 2SD601A/QR/-X | TRANSISTOR | | |

IC

| | | | | |
|--------|-----------------|-----------------|-----------|--|
| IC1301 | TDA9181T/N1-X | I.C(MONO-ANA) | | |
| IC1401 | LA78041 | I.C(MONO-ANA) | | |
| IC1461 | JLC1562BF-X | I C(DIGI-MOS) | | |
| IC1480 | UPC358G2-XE | IC(MONOLITHIC) | | |
| IC1601 | MSP3445G-QG-B8X | I.C(MONO-ANA) | | |
| IC1602 | NJW1136G-X | I.C(MONO-ANA) | | |
| IC1650 | AN7585 | I.C(MONO-ANA) | | |
| IC1701 | TDA9386N23I0956 | I.C(MCU) | | |
| IC1702 | AT24C08-25L33PH | I.C(MEMORY-OTH) | (SERVICE) | |
| IC1801 | MM1492AF | I.C(MONO-ANA) | | |
| IC1901 | STR-F6256S-F7 | I C(HYBRID) | | |
| IC1951 | SE135N | I C(HYBRID) | | |
| IC1972 | L88M33T-X | I.C(MONO-ANA) | | |
| IC1973 | BA17812T | I.C(MONO-ANA) | | |
| IC1974 | BA51W12ST-V5 | I.C(MONO-ANA) | | |

OTHERS

| | | | | |
|----------|--------------|---------------|--|--|
| CF1103 | QAX0639-001Z | C TRAP | | |
| △ CP1951 | ICP-N75-Y | IC PROTECTOR | | |
| △ CP1952 | ICP-N38-Y | IC PROTECTOR | | |
| △ CP1953 | ICP-N38-Y | IC PROTECTOR | | |
| J1801 | QNN0349-001 | PIN JACK | | |
| J1802 | QNN0349-002 | PIN JACK | | |
| J1803 | QNN0348-001 | PIN JACK | | |
| J1804 | QNN0349-001 | PIN JACK | | |
| J1805 | QNS0100-001 | 3.5 JACK | | |
| K1705 | QQR1214-001Y | FERRITE BEADS | | |
| K1901 | QQR1214-001Y | FERRITE BEADS | | |
| K1902 | QQR1214-001Y | FERRITE BEADS | | |
| K1903 | QQR1214-001Y | FERRITE BEADS | | |
| K1952 | QQR1214-001Y | FERRITE BEADS | | |
| K1953 | QQR1214-001Y | FERRITE BEADS | | |
| K1954 | QQR1214-001Y | FERRITE BEADS | | |

| △ Symbol No. | Part No. | Part Name | Description | Local |
|---------------|--------------|------------------|--------------|-------|
| OTHERS | | | | |
| K1955 | QQR1214-001Y | FERRITE BEADS | | |
| △ LF1901 | QQR1356-001 | LINE FILTER | | |
| △ PC1901 | PC123F2 | IC(PHOTO COUPLE) | | |
| △ RY1901 | QSK0061-001 | RELAY | | |
| SF1101 | QAX0663-001 | SAW FILTER | | |
| SF1102 | QAX0594-001 | SAW FILTER | | |
| TH1901 | QAD0145-2R3 | P THERMISTOR | | |
| TU1001 | QAU0251-002 | TUNER | | |
| W1010 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1031 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1032 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1239 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1257 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1306 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1307 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1309 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1321 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1325 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1326 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1333 | QQR1113-001Z | FERRITE BEADS | | |
| W1334 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1379 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1383 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1386 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1395 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1397 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1402 | QQR1113-001Z | FERRITE BEADS | | |
| W1405 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1418 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1423 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1428 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1430 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| W1431 | QQR1113-001Z | FERRITE BEADS | | |
| X1601 | CE42546-001Z | X TAL | | |
| X1701 | QAX0737-001 | CRYSTAL | | |
| Y1004 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| Y1602 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |
| Y1603 | NRSA63J-0R0X | MG R | 0.0Ω 1/16W J | |

CRT SOCKET PW BOARD ASS'Y (SCH-3005A-H2)

| △ Symbol No. | Part No. | Part Name | Description | Local |
|--|----------|-----------|-------------|-------|
| Refer to PARTS LIST in pages 49 - 51 for this PW BOARD | | | | |

FRONT CONTROL PW BOARD ASS'Y (SCH-8004A-H2)

| △ Symbol No. | Part No. | Part Name | Description | Local |
|--|----------|-----------|-------------|-------|
| Refer to PARTS LIST in pages 51 - 52 for this PW BOARD | | | | |

| △ | Symbol No. | Part No. | Part Name | Description | Local |
|---|------------|----------|-----------|-------------|-------|
|---|------------|----------|-----------|-------------|-------|


REMOTE CONTROL UNIT PARTS
LIST (RM-C1018-1H)

| △ | Ref.No | Part No. | Part Name | Description | Local |
|---|--------|----------|-----------|-------------|-------|
|---|--------|----------|-----------|-------------|-------|

| | | | | | |
|--|--|----------|---------------|--|--|
| | | 25-1168F | BATTERY COVER | | |
|--|--|----------|---------------|--|--|

| △ | Symbol No. | Part No. | Part Name | Description | Local |
|---|------------|----------|-----------|-------------|-------|
|---|------------|----------|-----------|-------------|-------|

PACKING



PACKING PARTS LIST

| △ Ref.No. | Part No. | Part Name | Description | Local |
|-----------|----------------|--------------------|--------------------------------|-------|
| 1 | CP30967-004-H | POLY BAG | | |
| 2 | GG10044-043A-H | P CASE | [AV-29W33 _{PH}] | |
| 2 | GG10044-051A-H | P CASE | [AV-29W33B _{PH}] | |
| 3 | GG10193-001C-H | CUSHION ASSY | | |
| 4 | RM-C1019-1H | RC HAND UNIT | [AV-29W33 _{PH}] | |
| 4 | RM-C1018-1H | RC HAND UNIT | [AV-29W33B _{PH}] | |
| 5 | CP30966-001-H | POLY BAG | | |
| △ 6 | LCT1180-001A-H | INST BOOK | | |
| 7 | GG10202-001A-H | BASS CUSHION | [AV-29W33B _{PH}] | |
| 8 | CP30967-007-H | POLY BAG | [AV-29W33B _{PH}] | |
| 9 | LC30946-001A-H | CRT PROTECTOR | | |
| 10 | LC30947-002A-H | CAUTION SHEET | | |
| 11 | GG20025-001A-H | CORNER LABEL | (x2) | |
| 12 | GG20011-008A-H | SUPPORT PAD(FRONT) | | |
| 13 | GG20011-009A-H | SUPPORT PAD(SIDE) | (x2) [AV-29W33 _{PH}] | |
| 13 | GG20011-009A-H | SUPPORT PAD(SIDE) | [AV-29W33B _{PH}] | |
| 14 | GG20011-010A-H | SUPPORT PAD(TOP) | [AV-29W33B _{PH}] | |