

PARTS LIST

CAUTION

- The parts identified by the \triangle symbol are important for the safety. Whenever replacing these parts, be sure to use specified ones to secure the safety.
- The parts not indicated in this Parts List and those which are filled with lines — in the Parts No. columns will not be supplied.
- P. W. Board Ass'y will not be supplied, but those which are filled with the Parts No. in the Parts No. columns will be supplied.

ABBREVIATIONS OF RESISTORS, CAPACITORS AND TOLERANCES

RESISTORS		CAPACITORS	
C R	Carbon Resistor	C CAP.	Ceramic Capacitor
F R	Fusible Resistor	E CAP.	Electrolytic Capacitor
P R	Plate Resistor	M CAP.	Mylar Capacitor
V R	Variable Resistor	HV CAP.	High Voltage Capacitor
HV R	High Voltage Resistor	MF CAP.	Metalized Film Capacitor
MF R	Metal Film Resistor	MM CAP.	Metalized Mylar Capacitor
MG R	Metal Glazed Resistor	MP CAP.	Metalized Polystyrol Capacitor
MP R	Metal Plate Resistor	PP CAP.	Polypropylene Capacitor
OM R	Metal Oxide Film Resistor	PS CAP.	Polystyrol Capacitor
CMF R	Coating Metal Film Resistor	TF CAP.	Thin Film Capacitor
UNF R	Non-Flammable Resistor	MPP CAP.	Metalized Polypropylene Capacitor
CH V R	Chip Variable Resistor	TAN. CAP.	Tantalum Capacitor
CH MG R	Chip Metal Glazed Resistor	CH C CAP.	Chip Ceramic Capacitor
COMP. R	Composition Resistor	BP E CAP.	Bi-Polar Electrolytic Capacitor
LPTC R	Linear Positive Temperature Coefficient Resistor	CH AL E CAP.	Chip Aluminum Electrolytic Capacitor
		CH AL BP CAP.	Chip Aluminum Bi-Polar Capacitor
		CH TAN. E CAP.	Chip Tantalum Electrolytic Capacitor
		CH AL BP E CAP.	Chip Tantalum Bi-Polar Electrolytic Capacitor

TOLERANCES									
F	G	J	K	M	N	R	H	Z	P
±1%	±2%	±5%	±10%	±20%	±30%	+30% -10%	+50% -10%	+80% -20%	+100% -0%

AV-32F703
AV-32F713
AV-32F803

CONTENTS

■ USING PW BOARD & REMOTE CONTROL UNIT	34
--	----

[AV-32F703/Y] [AV-32F713/Y] [AV-32F803/Y]

■ EXPLODED VIEW PARTS LIST	35,36
■ EXPLODED VIEW	35,37
■ PRINTED WIRING BOARD PARTS LIST	
● MAIN PW BOARD ASS'Y	38
● DAF PW BOARD ASS'Y	41
● CRT SOCKET PW BOARD ASS'Y	42
● PIP PW BOARD ASS'Y [AV-32F803/Y]	42
● AV SEL PW BOARD ASS'Y [AV-32F803/Y]	43
● AV SEL PW BOARD ASS'Y [AV-32F703/Y] [AV-32F713/Y]	44
● FRONT CONTROL PW BOARD ASS'Y	46
● LED & POWER SW PW BOARD ASS'Y	46
● 3D Y/C SEP MODULE PW BOARD ASS'Y [AV-32F803/Y]	46
■ REMOTE CONTROL UNIT PARTS LIST	46
■ PACKING	47
■ PACKING PARTS LIST	47

USING P.W. BOARD & REMOTE CONTROL UNIT

Model P.W.B ASS'Y	AV-32F 703/Y	AV-32F 713/Y	AV-32F 803/Y
MAIN PWB	SGJ-1012A-M2	SGJ-1011A-M2	SGJ-1010A-M2
DAF PWB	SGJ-2003A-M2	←	←
CRT SOCKET PWB	SGJ-3004A-M2	←	←
PIP PWB	—	—	SGJ-4001A-M2
AV SEL PWB	SGJ-5002A-M2	←	SGJ-5001A-M2
FRONT CONTROL PWB	SGJ-6002A-M2	←	←
LED & POWER SW PWB	SGJ-7001A-M2	←	←
3D Y/C SEP MODULE PWB	—	—	SGJ0Y001A-M2
REMOTE CONTROL UNIT	RM-C326G-1A	RM-C326-1A	RM-C325G-1A

EXPLODED VIEW PARTS LIST(1)

[AV-32F703/Y]

△ Ref.No.	Part No.	Part Name	Description
1	CM48006-008-C	JVC MARK	
2	LC30191-003A-A	REMOCON LENS	
△ 100	LC11048-003B-A	FRONT CABI ASSY(Silver)	Inc.No.101~105
△ 101	LC20628-001C-A	DOOR	
102	CM48229-00A-C	DOOR LATCH	
△ 103	LC31237-001A-A	KNOB(POWER)	
104	CM36481-002A-A	SPRING	
105	LC31238-004A-A	OPERATION SHEET	


[AV-32F713/Y]

△ Ref.No.	Part No.	Part Name	Description
1	CM48006-009-C	JVC MARK	
2	LC30191-003A-A	REMOCON LENS	
△ 100	LC11048-004A-A	FRONT CABI ASSY(Black)	Inc.No.101~105
△ 101	LC20628-002A-A	DOOR	
102	CM48229-00A-C	DOOR LATCH	
△ 103	LC31237-002A-A	KNOB(POWER)	
104	CM36481-002A-A	SPRING	
105	LC31238-005A-A	OPERATION SHEET	

[AV-32F803/Y]

△ Ref.No.	Part No.	Part Name	Description
1	CM48006-008-C	JVC MARK	
2	LC30191-003A-A	REMOCON LENS	
△ 100	LC11048-003B-A	FRONT CABI ASSY(Silver)	Inc.No.101~105
△ 101	LC20628-001C-A	DOOR	
102	CM48229-00A-C	DOOR LATCH	
△ 103	LC31237-001A-A	KNOB(POWER)	
104	CM36481-002A-A	SPRING	
105	LC31238-004A-A	OPERATION SHEET	

EXPLODED VIEW (1)



AV-32F703
AV-32F713
AV-32F803

EXPLODED VIEW PARTS LIST(2)

[AV-32F703/Y]

△ Ref.No.	Part No.	Part Name	Description
△ V01	A80AJZ90X03	ITC	Inc.DY,PC MAGNET,WEDGE
△ L01	QQW0107-001	DEG COIL	
△ T502	QQH0125-001	FB TRANSF	
3	A48457-4-S	SPRING	
4	WJY0016-002A	E-BRAIDED ASSY	
5	WJY0013-003A	E-BRAIDED SUB ASSY	
△ 6	LC20217-004B-A	CONTROL KNOB	
△ 7	QAS0101-001	SPEAKER	(x2)SP01-02
8	LC20629-001B-A	SP HOLDER	(x2)
9	CM48221-003-A	WASHER	(x8)
10	LC40226-002A-A	SPACER	(x4)
11	LC41029-001A-A	SCREW	(x4)
△ 12	LC10883-001C-A	CHASSIS BASE	
△ 13	LC20899-004A-A	TERMINAL BOARD	
14	QYSB5B3010Z	SCREW	(x4)
△ 15	QMPD200-200-JC	POWER CORD	or QMPD390-200-JS Within MAIN PWB(CNOPW)
△ 16	LC20106-001D-A	POWER CORD CLAMP	
△ 17	LC11042-001D-A	REAR COVER	
18	QYSB5FG4016Z	SCREW	(x12)
△ 19	GQ30032-001A-A	RATING LABEL	
△ 20	GQ30034-001B-A	WARNING LABEL	


[AV-32F713/Y]

△ V01	A80AJZ90X03	ITC	Inc.DY,PC MAGNET,WEDGE
△ L01	QQW0107-001	DEG COIL	
△ T502	QQH0125-001	FB TRANSF	
3	A48457-4-S	SPRING	
4	WJY0016-002A	E-BRAIDED ASSY	
5	WJY0013-003A	E-BRAIDED SUB ASSY	
△ 6	LC20217-006A-A	CONTROL KNOB	
△ 7	QAS0101-001	SPEAKER	(x2)SP01-02
8	LC20629-001B-A	SP HOLDER	(x2)
9	CM48221-003-A	WASHER	(x8)
10	LC40226-002A-A	SPACER	(x4)
11	LC41029-001A-A	SCREW	(x4)
△ 12	LC10883-001C-A	CHASSIS BASE	
△ 13	LC20899-004A-A	TERMINAL BOARD	
14	QYSB5B3010Z	SCREW	(x4)
△ 15	QMPD200-200-JC	POWER CORD	or QMPD390-200-JS Within MAIN PWB(CNOPW)
△ 16	LC20106-001D-A	POWER CORD CLAMP	
△ 17	LC11042-001D-A	REAR COVER	
18	QYSB5FG4016Z	SCREW	(x12)
△ 19	GQ30032-001A-A	RATING LABEL	
△ 20	GQ30034-001B-A	WARNING LABEL	

[AV-32F803/Y]

△ V01	A80AJZ90X03	ITC	Inc.DY,PC MAGNET,WEDGE
△ L01	QQW0107-001	DEG COIL	
△ T502	QQH0125-001	FB TRANSF	
3	A48457-4-S	SPRING	
4	WJY0016-002A	E-BRAIDED ASSY	
5	WJY0013-003A	E-BRAIDED SUB ASSY	
△ 6	LC20217-004B-A	CONTROL KNOB	
△ 7	QAS0101-001	SPEAKER	(x2)SP01-02
8	LC20629-001B-A	SP HOLDER	(x2)
9	CM48221-003-A	WASHER	(x8)
10	LC40226-002A-A	SPACER	(x4)
11	LC41029-001A-A	SCREW	(x4)
△ 12	LC10883-001C-A	CHASSIS BASE	
△ 13	LC20899-005A-A	TERMINAL BOARD	
14	QYSB5B3010Z	SCREW	(x6)
△ 15	QMPD200-200-JC	POWER CORD	or QMPD390-200-JS Within MAIN PWB(CNOPW)
△ 16	LC20106-001D-A	POWER CORD CLAMP	
△ 17	LC11042-001D-A	REAR COVER	
18	QYSB5FG4016Z	SCREW	(x12)
△ 19	GQ30032-001A-A	RATING LABEL	
△ 20	GQ30034-001B-A	WARNING LABEL	
21	WJX0014-002A	E-COAXIAL ASSY	[AV-32F803/Y ONLY]

EXPLODED VIEW (2)



AV-32F703
AV-32F713
AV-32F803

[AV-32F703Y] [AV-32F713Y] [AV-32F803Y]

PRINTED WIRING BOARD PARTS LIST

MAIN P.W. BOARD ASS'Y

(SGJ-1012A-M2)[AV-32F703Y] / (SGJ-1011A-M2)[AV-32F713Y] / (SGJ-1010A-M2)[AV-32F803Y]

Symbol No.	Part No.	Part Name	Description
△ CN0PW	QMPD00-200-JC	POWER CORD	
△ OR	QMPD00-200-JS	POWER CORD	
△ FR525	QRZ9017-4R7	F R	4.7Ω 1/4W J
△ FR527	QRZ9011-470	F R	47Ω 1/2W J
△ TU001	QAU0274-001	TUNER, 713Y/703Y	
△ TU001	QAU0272-001	TUNER, 803Y	
△ IC101	M523425P	IC	
△ IC201	TM8812CSBNG3U68	IC	
△ IC421	LA7841	IC	
△ IC601	TA1287F	IC, 803Y	
△ IC602	M52055FP	IC, 803Y	
△ IC621	LA4485	IC	
△ IC702	AT24C08-32F80B	IC	(SERVICE)
△ IC708	S-80840CNY-T	IC	
△ IC704	AN78L05	IC	
△ IC851	AN78L2F	IC	
△ OR	BA17812T	IC	
△ IC852	AN7809F	IC	
△ OR	BA17809T	IC	
△ IC853	AN7805F	IC	
△ OR	BA17805T	IC	
△ IC911	STR-F6626/F3	IC	
△ IC921	SE135N	IC	
△ Q001	UN2212	DIGI TRANSISTOR	
△ Q101	2SC5083/L-P/-T	TRANSISTOR	
△ Q131	2SB709A/QR/-X	TRANSISTOR	
△ Q161	2SD601A/QR/-X	TRANSISTOR	
△ Q211	2SD601A/QR/-X	TRANSISTOR	
△ Q232	2SD601A/QR/-X	TRANSISTOR	
△ Q233	2SD601A/QR/-X	TRANSISTOR	
△ Q352	2SD601A/QR/-X	TRANSISTOR	
△ Q353	2SD601A/QR/-X	TRANSISTOR	
△ Q431	UN2212	DIGI TRANSISTOR	
△ Q451	2SD601A/QR/-X	TRANSISTOR	
△ Q501	2SC4212/Z1	TRANSISTOR	
△ Q511	2SD2645-YD	POWER TRANSISTO	H. OUT
△ Q531	2SC2785/JH/-T	SI TRANSISTOR	
△ Q532	2SB709A/QR/-X	TRANSISTOR	
△ Q541	2SB709A/QR/-X	TRANSISTOR	
△ Q542	2SB709A/QR/-X	TRANSISTOR	
△ Q543	2SD1408/OY/-LB	POW TRANSISTOR	
△ Q622	2SD601A/QR/-X	TRANSISTOR	
△ Q623	UN2212	DIGI TRANSISTOR	
△ Q700	2SD601A/QR/-X	TRANSISTOR, 803Y	
△ Q701	2SB709A/QR/-X	TRANSISTOR	
△ Q705	2SD601A/QR/-X	TRANSISTOR, 803Y	
△ Q951	2SD1383K/AB/-X	TRANSISTOR	
△ Q971	2SA1208/ST/Z1-T	TRANSISTOR	
△ D305	1SS133	DIODE	
△ D306	1SS133	DIODE	
△ D307	1SS133	DIODE	
△ D308	1SS133	DIODE	
△ D309	1SS133	DIODE	
△ D310	1SS133	DIODE	
△ D352	MTZJ9.1C	ZENER DIODE	
△ D353	1SS133	DIODE	
△ D354	MTZJ3.3A	ZENER DIODE	
△ D421	1N4003	DIODE	
△ D422	MTZJ75	ZENER DIODE, 803Y	
△ D431	1SR35-400A-T2	DIODE	
△ D432	1SS133	DIODE	
△ D501	RH3G-F1	DIODE	
△ D502	RU3M-LFC4	DIODE	
△ D507	RGP10J-5025-T3	DIODE	
△ D521	RH15-T3	DIODE	
△ D523	EL12-T3	DIODE	
△ D524	EL12-T3	DIODE	
△ D525	1SS81-T5	DIODE	
△ D526	1SS81-T5	DIODE	
△ D527	1SR124-400A-T2	DIODE	
△ D529	MTZJ9.1C	ZENER DIODE	
△ D531	MA4068N/Z1/-T2	ZENER DIODE	
△ D534	QUY153-050Y	IM BUS WIRE	
△ D535	1SS133	DIODE	
△ D537	1SR35-400A-T2	DIODE	
△ D601	MTZJ9.1C	ZENER DIODE	
△ D602	MTZJ9.1C	ZENER DIODE	
△ D603	MTZJ9.1C	ZENER DIODE	
△ D604	MTZJ9.1C	ZENER DIODE, 803Y	
△ D605	MTZJ9.1C	ZENER DIODE, 803Y	

Symbol No.	Part No.	Part Name	Description
△ D606	MTZJ9.1C	ZENER DIODE, 803Y	
△ D653	1SS133	DIODE, 803Y	
△ D654	1SS133	DIODE, 803Y	
△ D700	MTZJ5.6B	ZENER DIODE	
△ D701	1SS133	DIODE	
△ D703	MTZJ5.6B	ZENER DIODE	
△ D704	MTZJ5.6B	ZENER DIODE	
△ D705	1SS133	DIODE	
△ D706	MTZJ5.6B	ZENER DIODE	
△ D707	MTZJ5.6B	ZENER DIODE	
△ D708	MTZJ5.6B	ZENER DIODE	
△ D709	MTZJ5.6B	ZENER DIODE	
△ D721	1SS133	DIODE, 803Y	
△ D722	1SS133	DIODE, 803Y	
△ D723	MTZJ5.6B	ZENER DIODE	
△ D810	MTZJ5.6B	ZENER DIODE	
△ D901	GS1B460-S1	BRIDGE DIODE	
△ D910	MA700A	SB DIODE	
△ D911	RGP10J-5025-T3	DIODE	
△ D912	RGP10J-5025-T3	DIODE	
△ D913	RGP10J-5025-T3	DIODE	
△ D914	1SS133	DIODE	
△ D915	SAR501	DIODE	
△ D917	MTZJ30A	ZENER DIODE	
△ D918	MTZJ5.1C	ZENER DIODE	
△ D920	1SS133	DIODE	
△ D931	RU30A-F1	DIODE	
△ D933	RU3Y-LFC4	DIODE	
△ D935	RU3Y-LFC4	DIODE	
△ D937	RU3Y-LFC4	DIODE	
△ D941	MTZJ33A	ZENER DIODE	
△ D945	MTZJ9.1B	ZENER DIODE	
△ D952	1SS133	DIODE	
△ D953	1SS133	DIODE	
△ D954	1SR35-400A-T2	DIODE	
△ D955	1SR35-400A-T2	DIODE	
△ D956	1SR35-400A-T2	DIODE	
△ D957	1SR35-400A-T2	DIODE	
△ D972	MTZJ15C	ZENER DIODE	
△ D973	1SS133	DIODE	
△ R002	NRS463J-0R0X	MG R	0.0Ω 1/16W J
△ R003	NRS463J-101X	MG R	10Ω 1/16W J
△ R004	NRS463J-101X	MG R	10Ω 1/16W J
△ R005	NRS463J-0R0X	MG R	0.0Ω 1/16W J
△ R008	NRS463J-820X	MG R	82Ω 1/16W J
△ R009	NRS463J-682X	MG R	6.8kΩ 1/16W J
△ R101	NRS463J-562X	MG R	5.6kΩ 1/16W J
△ R102	NRS463J-182X	MG R	1.8kΩ 1/16W J
△ R103	QRE121J-101Y	C R	10Ω 1/2W J
△ R104	NRS463J-180X	MG R	18Ω 1/16W J
△ R105	NRS463J-270X	MG R	27Ω 1/16W J
△ R111	NRS463J-394X	MG R	390kΩ 1/16W J
△ R112	NRS463J-334X	MG R	330kΩ 1/16W J
△ R113	NRS463J-101X	MG R	10Ω 1/16W J
△ R115	NRS463J-101X	MG R	10Ω 1/16W J
△ R116	NRS463J-680X	MG R	68Ω 1/16W J
△ R117	NRS463J-273X	MG R	27kΩ 1/16W J
△ R118	NRS463J-223X	MG R	22kΩ 1/16W J
△ R131	NRS463J-102X	MG R	1kΩ 1/16W J
△ R132	NRS463J-331X	MG R	33Ω 1/16W J
△ R133	NRS463J-821X	MG R	82Ω 1/16W J
△ R134	NRS463J-561X	MG R	56Ω 1/16W J
△ R135	NRS463J-102X	MG R	1kΩ 1/16W J
△ R161	NRS463J-332X	MG R	3.3kΩ 1/16W J
△ R162	NRS463J-0R0X	MG R	0.0Ω 1/16W J
△ R163	NRS463J-223X	MG R	22kΩ 1/16W J
△ R164	NRS463J-102X	MG R	1kΩ 1/16W J
△ R165	NRS463J-223X	MG R	22kΩ 1/16W J
△ R166	NRS463J-103X	MG R	10kΩ 1/16W J
△ R167	NRS463J-102X	MG R	1kΩ 1/16W J
△ R168	NRS463J-101X	MG R	10Ω 1/16W J
△ R169	NRS463J-561X	MG R	56Ω 1/16W J
△ R171	NRS463J-103X	MG R	10kΩ 1/16W J
△ R201	NRS463J-223X	MG R	22kΩ 1/16W J
△ R212	NRS463J-272X	MG R	2.7kΩ 1/16W J
△ R215	NRS463J-562X	MG R	5.6kΩ 1/16W J
△ R216	NRS463J-562X	MG R	5.6kΩ 1/16W J

△ Symbol No.	Part No.	Part Name	Description
R217	NRS463J-102X	MG R	1kΩ 1/16W J
R222	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R227	NRS463J-104X	MG R	100kΩ 1/16W J
R231	NRS463J-182X	MG R	1.8kΩ 1/16W J
R237	NRS463J-392X	MG R	3.9kΩ 1/16W J
R238	NRS463J-473X	MG R	47kΩ 1/16W J
R241	NRS463J-332X	MG R	3.3kΩ 1/16W J
R243	NRS463J-152X	MG R	1.5kΩ 1/16W J
R281	NRS463J-182X	MG R	1.8kΩ 1/16W J
R282	NRS463J-392X	MG R	3.9kΩ 1/16W J
R283	NRS463J-681X	MG R	680Ω 1/16W J
R286	NRS463J-472X	MG R	4.7kΩ 1/16W J
R287	NRS463J-101X	MG R	100Ω 1/16W J
R288	NRS402J-471X	MG R	470Ω 1/10W J
R289	NRS463J-154X	MG R	150kΩ 1/16W J
R290	NRS402J-561X	MG R	560Ω 1/10W J
R292	NRS463J-124X	MG R	120kΩ 1/16W J
R293	NRS463J-224X	MG R	220kΩ 1/16W J
R301	NRS463J-222X	MG R	2.2kΩ 1/16W J
R302	NRS463J-222X	MG R	2.2kΩ 1/16W J
R303	NRS463J-222X	MG R	2.2kΩ 1/16W J
R304	NRS463J-101X	MG R	100Ω 1/16W J
R305	NRS463J-101X	MG R	100Ω 1/16W J
R306	NRS463J-101X	MG R	100Ω 1/16W J
R318	NRS463J-472X	MG R	4.7kΩ 1/16W J
R319	NRS463J-102X	MG R	1kΩ 1/16W J
R352	NRS463J-103X	MG R	10kΩ 1/16W J
R354	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R355	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R356	NRS463J-123X	MG R	12kΩ 1/16W J
R358	NRS463J-333X	MG R	33kΩ 1/16W J
R359	NRS463J-103X	MG R	10kΩ 1/16W J
R360	NCB31HK-103X	C CAP.	0.01μF 50V K
R421	NRS463J-822X	MG R	8.2kΩ 1/16W J
R426	NRS463J-103X	MG R	10kΩ 1/16W J
R427	QRT09J-1R0	MF R	1.0Ω 2W J
R431	NRS463J-103X	MG R	10kΩ 1/16W J
R432	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R433	NRS463J-332X	MG R	3.3kΩ 1/16W J
R434	QRL09J-221	OM R	220Ω 2W J
R446	QRE121J-272Y	C R	2.7kΩ 1/2W J
R447	NRS463J-104X	MG R	100kΩ 1/16W J
R448	NRS463J-473X	MG R	47kΩ 1/16W J
R449	NRS463J-822X	MG R	8.2kΩ 1/16W J
R451	NRS463J-101X	MG R	100Ω 1/16W J
R452	NRS463J-103X	MG R	10kΩ 1/16W J
R501	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R502	NRS463J-271X	MG R	270Ω 1/16W J
R503	QRE121J-103Y	C R	10kΩ 1/2W J
R504	QRL09J-152	OM R	1.5kΩ 3W J
R505	QRL09J-152	OM R	1.5kΩ 3W J
R511	QRE121J-220Y	C R	22Ω 1/2W J
R512	QRE121J-681Y	C R	680Ω 1/2W J
R513	QRL09J-273	OM R	27kΩ 3W J
R516	QRZ021-2R0	OM R	2.0Ω 7W K
R524	NRS463J-563X	MG R	56kΩ 1/16W J
R526	QRE121J-272Y	C R	2.7kΩ 1/2W J
R527	QRE121J-124Y	C R	120kΩ 1/2W J
R528	QRE121J-154Y	C R	150kΩ 1/2W J
R529	NRS463J-331X	MG R	330Ω 1/16W J
R531	QRJ146J-391X	C R	390Ω 1/4W J
R532	NRS463J-273X	MG R	27kΩ 1/16W J
R533	NRS463J-123X	MG R	12kΩ 1/16W J
R534	NRS463J-123X	MG R	12kΩ 1/16W J
△ R535	NRV402D-242X	MF R	2.4kΩ 1/10W D
△ R537	NRV402D-752X	MF R	7.5kΩ 1/10W D
R538	NRS463J-333X	MG R	33kΩ 1/16W J
R543	QRE121J-122Y	C R	1.2kΩ 1/2W J
R544	QRE121J-392Y	C R	3.9kΩ 1/2W J
R545	QRE121J-822Y	C R	8.2kΩ 1/2W J
R546	NRS463J-331X	MG R	330Ω 1/16W J
R547	NRS463J-104X	MG R	100kΩ 1/16W J
R548	QRE121J-152Y	C R	1.5kΩ 1/2W J
R553	QRL09J-390	OM R	39Ω 3W J
△ R554	QRK126J-150X	C R	15Ω 1/2W J
R555	QRX029J-1R0	MF R	1.0Ω 2W J
R556	QRX029J-1R0	MF R	1.0Ω 2W J
R601	NRS463J-750X	MG R	75Ω 1/16W J
R602	NRS463J-750X	MG R	75Ω 1/16W J

△ Symbol No.	Part No.	Part Name	Description
R603	NRS463J-750X	MG R	75Ω 1/16W J
R604	NRS463J-750X	MG R	75Ω 1/16W J, 803Y
R605	NRS463J-750X	MG R	75Ω 1/16W J, 803Y
R606	NRS463J-750X	MG R	75Ω 1/16W J, 803Y
R610	NRS463J-0R0X	MG R	0.0Ω 1/16W J, 713Y/703Y
R611	NRS463J-0R0X	MG R	0.0Ω 1/16W J, 713Y/703Y
R614	NRS463J-682X	MG R	6.8kΩ 1/16W J, 803Y
R615	NRS463J-332X	MG R	3.3kΩ 1/16W J, 803Y
R616	NRS463J-332X	MG R	3.3kΩ 1/16W J, 803Y
R617	NRS463J-332X	MG R	3.3kΩ 1/16W J, 803Y
R618	NRS463J-332X	MG R	3.3kΩ 1/16W J, 803Y
R621	NRS463J-682X	MG R	6.8kΩ 1/16W J
R622	NRS463J-681X	MG R	680Ω 1/16W J
R623	NRS463J-682X	MG R	6.8kΩ 1/16W J
R624	NRS463J-681X	MG R	680Ω 1/16W J
R626	NRS463J-223X	MG R	22kΩ 1/16W J
R627	NRS463J-223X	MG R	22kΩ 1/16W J
R631	NRS463J-333X	MG R	33kΩ 1/16W J
R632	NRS463J-223X	MG R	22kΩ 1/16W J
R638	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R639	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R651	NRS463J-0R0X	MG R	0.0Ω 1/16W J, 713Y/703Y
R652	NRS463J-0R0X	MG R	0.0Ω 1/16W J, 713Y/703Y
R653	NRS463J-0R0X	MG R	0.0Ω 1/16W J, 713Y/703Y
R655	NRS463J-153X	MG R	15kΩ 1/16W J, 803Y
R700	NRS463J-102X	MG R	1kΩ 1/16W J
R701	NRS463J-103X	MG R	10kΩ 1/16W J
R702	NRS463J-102X	MG R	1kΩ 1/16W J
R704	NRS463J-472X	MG R	4.7kΩ 1/16W J
R705	NRS463J-472X	MG R	4.7kΩ 1/16W J
R706	NRS463J-472X	MG R	4.7kΩ 1/16W J
R707	NRS463J-103X	MG R	10kΩ 1/16W J
R708	NRS463J-101X	MG R	100Ω 1/16W J
R709	NRS463J-101X	MG R	100Ω 1/16W J
R714	NRS463J-823X	MG R	82kΩ 1/16W J, 803Y
R715	NRS463J-103X	MG R	10kΩ 1/16W J
R718	NRS463J-223X	MG R	22kΩ 1/16W J
R721	NRS463J-102X	MG R	1kΩ 1/16W J
R728	NRS463J-102X	MG R	1kΩ 1/16W J
R729	NRS463J-223X	MG R	22kΩ 1/16W J
R731	NRS463J-101X	MG R	100Ω 1/16W J
R732	NRS463J-101X	MG R	100Ω 1/16W J
R733	NRS463J-472X	MG R	4.7kΩ 1/16W J
R734	NRS463J-472X	MG R	4.7kΩ 1/16W J
R737	NRS463J-472X	MG R	4.7kΩ 1/16W J, 803Y
R739	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R740	NRS463J-103X	MG R	10kΩ 1/16W J
R754	NRS463J-472X	MG R	4.7kΩ 1/16W J, 803Y
R755	NRS463J-153X	MG R	15kΩ 1/16W J, 803Y
R756	NRS463J-103X	MG R	10kΩ 1/16W J, 803Y
R764	NRS463J-221X	MG R	22Ω 1/16W J
R765	NRS463J-221X	MG R	22Ω 1/16W J
R766	NRS463J-221X	MG R	22Ω 1/16W J
R767	NRS463J-221X	MG R	22Ω 1/16W J
R769	NRS463J-682X	MG R	6.8kΩ 1/16W J
R772	NRS463J-103X	MG R	10kΩ 1/16W J
R775	NRS463J-473X	MG R	47kΩ 1/16W J, 803Y
R776	NRS463J-103X	MG R	10kΩ 1/16W J, 803Y
R811	NRS463J-473X	MG R	47kΩ 1/16W J
R812	NRS463J-102X	MG R	1kΩ 1/16W J
R816	NRS463J-124X	MG R	120kΩ 1/16W J
R821	NRS463J-184X	MG R	180kΩ 1/16W J
R822	NRS463J-0R0X	MG R	0.0Ω 1/16W J, 713Y/703Y
R822	NRS463J-124X	MG R	120kΩ 1/16W J, 803Y
R827	NRS463J-102X	MG R	1kΩ 1/16W J
R857	QRL029J-820	OM R	82Ω 2W J
R858	QRL029J-180	OM R	18Ω 2W J, 803Y
△ R901	QRF074K-R47	UNF R	0.47Ω 7W K
△ R909	QRG01GJ-470	OM R	47Ω 1W J
R911	QRE121J-223Y	C R	22kΩ 1/2W J
R912	QRT029J-R18	MF R	0.18Ω 2W J
R913	QRT029J-R15	MF R	0.15Ω 2W J
△ R914	QRK126J-681X	C R	680Ω 1/2W J
△ R915	QRK129J-6R8	C R	6.8Ω 1/2W J
△ R917	QRK126J-332X	C R	3.3kΩ 1/2W J
R918	QRE121J-222Y	C R	2.2kΩ 1/2W J
R919	QRE121J-684Y	C R	680kΩ 1/2W J
R924	QRE121J-222Y	C R	2.2kΩ 1/2W J
R930	QRE121J-223Y	C R	22kΩ 1/2W J

AV-32F703
AV-32F713
AV-32F803

△ Symbol No.	Part No.	Part Name	Description
R940	QRE121J-181Y	C R	180Ω 1/2W J
R941	QRL029J-183	OM R	18kΩ 2W J
R950	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R951	NRS463J-473X	MG R	47kΩ 1/16W J
R952	NRS463J-102X	MG R	1kΩ 1/16W J
R953	QRE121J-820Y	C R	82Ω 1/2W J
R954	QUY160-100Y	IM BUS WIRE	
R973	QRE121J-272Y	C R	2.7kΩ 1/2W J
R975	QRE121J-223Y	C R	22kΩ 1/2W J
R977	QRE121J-473Y	C R	47kΩ 1/2W J
R978	NRS463J-333X	MG R	33kΩ 1/16W J
R979	QRT029J-1R0	MF R	1.0Ω 2W J
R980	QRT029J-1R0	MF R	1.0Ω 2W J
R998	QRZ9041-275	C R	2.7MΩ 1/2W K
R999	QRE121J-121Y	C R	120Ω 1/2W J
C001	QETN1LM-475	E CAP.	4.7μF 50V M
C003	QETN1LM-106	E CAP.	10μF 50V M
C004	QETN1LM-108	E CAP.	1000μF 16V M
C006	QETN1LM-476	E CAP.	47μF 25V M
C101	NCB31HK-103X	C CAP.	0.01μF 50V K
C102	NCB31HK-103X	C CAP.	0.01μF 50V K
C104	NCB31HK-103X	C CAP.	0.01μF 50V K
C105	NCB31HK-103X	C CAP.	0.01μF 50V K
C106	QETN1LM-476	E CAP.	47μF 25V M
C107	NCB31HK-103X	C CAP.	0.01μF 50V K
C113	NCB31HK-103X	C CAP.	0.01μF 50V K
C114	NCB31HK-103X	C CAP.	0.01μF 50V K
C116	QFV1HJ-224Z	MF CAP.	0.22μF 50V J
C117	QETN1LM-476	E CAP.	47μF 25V M
C118	NCB31HK-103X	C CAP.	0.01μF 50V K
C119	NDC31HJ-681X	C CAP.	680pF 50V J
C120	QETN1LM-474	E CAP.	0.47μF 50V M
C124	NCB31HK-103X	C CAP.	0.01μF 50V K
C131	NCB31HK-103X	C CAP.	0.01μF 50V K
C161	QETN1LM-106	E CAP.	10μF 50V M
C163	NDC31HJ-470X	C CAP.	47pF 50V J
C164	NDC31HJ-470X	C CAP.	47pF 50V J
C165	NCB31HK-103X	C CAP.	0.01μF 50V K
C166	NCB31HK-103X	C CAP.	0.01μF 50V K
C202	QETN1LM-105	E CAP.	1μF 50V M
C203	NCB31HK-152X	C CAP.	1500pF 50V K
C211	QEN1CM-106	E CAP.	10μF 16V M
C212	NDC31HJ-100X	C CAP.	10pF 50V J
C221	QETN1LM-106	E CAP.	10μF 50V M
C222	QFV1HJ-104Z	MF CAP.	0.1μF 50V J
C223	NCB31HK-103X	C CAP.	0.01μF 50V K
C233	NDC31HJ-680X	C CAP.	68pF 50V J
C237	NCB31HK-103X	C CAP.	0.01μF 50V K
C241	NCB31HK-103X	C CAP.	0.01μF 50V K
C242	QETN1LM-225	E CAP.	2.2μF 50V M
C243	QETN1LM-107	E CAP.	100μF 16V M
C244	NCB31HK-103X	C CAP.	0.01μF 50V K
C281	QFV1HJ-474Z	MF CAP.	0.47μF 50V J
C282	QETN1LM-107	E CAP.	100μF 16V M
C283	NCB31HK-103X	C CAP.	0.01μF 50V K
C284	QETN1LM-225	E CAP.	2.2μF 50V M
C285	NCB31HK-103X	C CAP.	0.01μF 50V K
C286	QETN1LM-106	E CAP.	10μF 50V M
C287	QETN1LM-107	E CAP.	100μF 16V M
C288	NCB31HK-103X	C CAP.	0.01μF 50V K
C302	NCB31EK-104X	C CAP.	0.1μF 25V K
C352	QETN1LM-476	E CAP.	47μF 16V M
C354	NCB31HK-103X	C CAP.	0.01μF 50V K
C391	QETN1LM-107	E CAP.	100μF 16V M
C392	NCB31HK-103X	C CAP.	0.01μF 50V K
C422	QFN32AK-102	M CAP.	1000pF 100V K
C424	QETN1LM-107	E CAP.	100μF 35V M
C428	QEHQ1VM-108	E CAP.	1000μF 35V M
C431	QFLC2AK-563Z	M CAP.	0.056μF 100V K
C432	QETN1LM-476	E CAP.	47μF 25V M
C433	QETN1LM-476	E CAP.	47μF 25V M
C435	NCB31HK-183X	C CAP.	0.018μF 50V K
C440	QCS32HJ-180	C CAP.	18pF 500V J
C501	QCB32HK-151	C CAP.	150pF 500V K
C502	QCB32HK-331	C CAP.	330pF 500V K
C503	QEHRCM-105	E CAP.	1μF 160V M
C504	QEZ0203-107	E CAP.	100μF 160V M
C505	QENC2AM-225	E CAP.	2.2μF 100V M
C507	QEZ0195-475Z	E CAP.	4.7μF 50V M

△ Symbol No.	Part No.	Part Name	Description
C510	QFZ0200-422	MPP CAP.	4200pF 1.5kVH±3%
C513	QFZ0198-153	MPP CAP.	0.015μF 1.5kVH±3%
C514	QFP32GJ-223	PP CAP.	0.02μF 400V J
C515	QFZ0197-474	MPP CAP.	0.47μF 250V J
△ OR	QFZ0199-474	MPP CAP.	0.47μF 250V J
C516	QCB32HK-561	C CAP.	560pF 500V K
C521	QETN2EM-106	E CAP.	10μF 250V M
C523	QETN1EM-108	E CAP.	1000μF 25V M
C524	QETN1EM-108	E CAP.	1000μF 25V M
C525	QETN1VM-107	E CAP.	100μF 35V M
C526	QFV21HJ-824	MF CAP.	0.82μF 50V J
C527	QFLC2AJ-103Z	M CAP.	0.01μF 100V J
C533	QETN1LM-106	E CAP.	10μF 50V M
C601	QETN1EM-476	E CAP.	47μF 25V M
C602	QETN1EM-476	E CAP.	47μF 25V M
C603	QETN1EM-476	E CAP.	47μF 25V M
C604	NCB31EK-104X	C CAP.	0.1μF 25V K, 803Y
C605	NCB31EK-104X	C CAP.	0.1μF 25V K, 803Y
C606	NCB31EK-104X	C CAP.	0.1μF 25V K, 803Y
C607	QETN1AM-477	E CAP.	470μF 10V M, 803Y
C608	NCB31HK-103X	C CAP.	0.01μF 50V K, 803Y
C609	QFV1HJ-104Z	MF CAP.	0.1μF 50V J
C610	QFV1HJ-104Z	MF CAP.	0.1μF 50V J
C611	QFV1HJ-104Z	MF CAP.	0.1μF 50V J
C612	QETN1EM-476	E CAP.	47μF 25V M, 803Y
C613	QETN1EM-476	E CAP.	47μF 25V M, 803Y
C614	QETN1EM-476	E CAP.	47μF 25V M, 803Y
C615	QETN1AM-477	E CAP.	470μF 10V M, 803Y
C616	NCB31HK-103X	C CAP.	0.01μF 50V K, 803Y
C621	NCB31HK-102X	C CAP.	1000pF 50V K
C622	NCF21CZ-105X	C CAP.	1μF 16V Z
C623	NCB31HK-102X	C CAP.	1000pF 50V K
C624	NCF21CZ-105X	C CAP.	1μF 16V Z
C625	QETN1CM-107	E CAP.	100μF 16V M
C626	QETN1EM-108	E CAP.	1000μF 25V M
C627	QETN1LM-474	E CAP.	0.47μF 50V M
C628	QETN1EM-108	E CAP.	1000μF 25V M
C629	QETN1EM-108	E CAP.	1000μF 25V M
C636	QETN1LM-105	E CAP.	1μF 50V M
C637	QETN1LM-105	E CAP.	1μF 50V M
C652	NCB31EK-104X	C CAP.	0.1μF 25V K, 803Y
C653	NCB31EK-104X	C CAP.	0.1μF 25V K, 803Y
C654	NCB31EK-104X	C CAP.	0.1μF 25V K, 803Y
C655	NCB31HK-103X	C CAP.	0.01μF 50V K, 803Y
C656	NDC31HJ-150X	C CAP.	15pF 50V J, 803Y
C657	NDC31HJ-150X	C CAP.	15pF 50V J, 803Y
C658	NDC31HJ-150X	C CAP.	15pF 50V J, 803Y
C700	NCB31HK-102X	C CAP.	1000pF 50V K
C701	QETN1LM-106	E CAP.	10μF 50V M
C702	QETN1LM-106	E CAP.	10μF 50V M
C703	QETN1LM-106	E CAP.	10μF 50V M
C704	QETN1CM-107	E CAP.	100μF 16V M
C705	NCB31HK-103X	C CAP.	0.01μF 50V K
C706	QETN1LM-105	E CAP.	1μF 50V M
C708	NDC31HJ-220X	C CAP.	22pF 50V J
C709	NDC31HJ-220X	C CAP.	22pF 50V J
C711	QETN1CM-107	E CAP.	100μF 16V M
C712	NCB31HK-103X	C CAP.	0.01μF 50V K
C716	QETN1LM-106	E CAP.	10μF 50V M
C721	NCB31HK-103X	C CAP.	0.01μF 50V K, 803Y
C726	NDC31HJ-561X	C CAP.	560pF 50V J, 803Y
C728	NCB31HK-103X	C CAP.	0.01μF 50V K
C807	QETN1AM-477	E CAP.	470μF 10V M
OR	QETN1LM-106	E CAP.	10μF 50V M
C813	NCB31HK-102X	C CAP.	1000pF 50V K
C815	NCB31HK-103X	C CAP.	0.01μF 50V K
C851	QETN1EM-107	E CAP.	100μF 25V M
C852	QETN1EM-107	E CAP.	100μF 25V M
C853	QETN1CM-227	E CAP.	220μF 16V M
C854	QETN1CM-227	E CAP.	220μF 16V M
C856	QETN1CM-227	E CAP.	220μF 16V M
C857	QETN1CM-477	E CAP.	470μF 16V M
△ C901	QFZ9075-104	MPP CAP.	0.1μFAC275V M
△ OR	QFZ9072-104	MF CAP.	0.1μFAC275V K
△ C902	QFZ9072-473	MF CAP.	0.047μFAC275V K
△ OR	QFZ9075-473	MPP CAP.	0.047μFAC275V M
△ C903	QFZ9075-104	MPP CAP.	0.1μFAC275V M
△ OR	QFZ9072-104	MF CAP.	0.1μFAC275V K
△ C904	QFZ9054-102	C CAP.	1000pFAC250V Z

Symbol No.	Part No.	Part Name	Description
△ C905	QCZ9054-102	C CAP.	1000pFAC250V Z
△ C906	QCZ9054-102	C CAP.	1000pFAC250V Z
△ C907	QEZ0169-477	E CAP.	470uF 200V M
△ C908	QCZ9054-102	C CAP.	1000pFAC250V Z
OR	QCZ9079-102	C CAP.	1000pFAC250V M
△ C912	QCZ0340-222	C CAP.	2200pF 2kV K
△ C913	QFLCHJ-4712	M CAP.	470uF 50V J
C914	QETNLM-107	E CAP.	100uF 50V M
C916	NDC31HJ-331X	C CAP.	330pF 50V J
C917	NCB31HK-182X	C CAP.	1800pF 50V K
C918	NCB21HK-104X	C CAP.	0.1uF 50V K
C919	QFP32GJ-103	PP CAP.	0.01uF 400V J
C931	QEZ0203-227	E CAP.	220uF 160V M
C932	QETNLEM-108	E CAP.	1000uF 25V M
C933	QETNLEM-108	E CAP.	1000uF 16V M
C934	NDC31HJ-221X	C CAP.	220pF 50V J
C935	QETNLEM-108	E CAP.	1000uF 25V M
C937	QCZ0340-102	C CAP.	1000pF 2kV K
C938	QETNLEM-228	E CAP.	2200uF 25V M
OR	QETNLEM-108	E CAP.	1000uF 16V M
C939	QCB32HK-152	C CAP.	1500pF 500V K
C941	QCB32HK-102	C CAP.	1000pF 500V K
C942	QEHRLHM-105	E CAP.	1uF 50V M
C943	QETNLEM-108	E CAP.	1000uF 16V M
C951	QETNLEM-477	E CAP.	470uF 25V M
C952	QETNLEM-227	E CAP.	220uF 16V M
C971	QETNLEM-107	E CAP.	100uF 16V M
C972	QETNLEM-476	E CAP.	47uF 25V M
C973	QETNLM-106	E CAP.	10uF 50V M
△ C997	QCZ9052-102	C CAP.	1000pFAC125V M
△ OR	QCZ9079-102	C CAP.	1000pFAC250V M
△ C998	QCZ9074-103	C CAP.	0.01uFAC250V M
△ C999	QCZ9074-103	C CAP.	0.01uFAC250V M
L001	QQL244K-560Z	COIL	56uH K
L101	QQL2014-R22	COIL	
L113	QQL244K-4R7Z	COIL	4.7uH K
L131	QQL244K-150Z	COIL	15uH K
L161	QQL244K-220Z	COIL	22uH K
L232	QQL244K-560Z	COIL	56uH K
L241	QQL244K-220Z	COIL	22uH K
L391	QQL244K-220Z	COIL	22uH K
△ L511	QQR1027-005	LINEARITY COIL	
△ L512	QQL2036-821	COIL	
△ L521	QQL2018-800	COIL	
L701	QQL244K-220Z	COIL	22uH K
L702	QQL244K-220Z	COIL	22uH K
L703	QQL244K-220Z	COIL	22uH K
L704	QQL244K-220Z	COIL	22uH K
L705	QQL244K-220Z	COIL	22uH K
L931	QQL26AK-470Z	COIL	47uH K
L933	QQL26AK-470Z	COIL	47uH K
L937	QQL26AK-470Z	COIL	47uH K
L940	QQR0582-001Z	FERRITE BEADS	
CF001	QAX0349-001	C TRAP	
CF131	QAX0639-001Z	C TRAP	
CF161	QAX0642-001Z	CERAMIC FILTER	
LC601	QQR1199-001	N FILTER	
LC602	QQR1199-001	N FILTER	
LC603	QQR1199-001	N FILTER	
LC604	QQR1199-001	N FILTER, 803Y	
LC605	QQR1199-001	N FILTER, 803Y	
LC606	QQR1199-001	N FILTER, 803Y	
X701	QAX0717-001Z	CRYSTAL RESONATOR	
K401	QQR0621-002Z	FERRITE BEADS	
K912	QQR0582-001Z	FERRITE BEADS	
K914	QUY153-050Y	IM BUS WIRE	
K916	QQR0582-001Z	FERRITE BEADS	
K917	QQR0582-001Z	FERRITE BEADS	
K918	QQR0582-001Z	FERRITE BEADS	
K920	QQR0872-002	FERRITE BEADS	
K931	QQR0582-001Z	FERRITE BEADS	
K932	QQR0582-001Z	FERRITE BEADS	
K933	QQR0582-001Z	FERRITE BEADS	
K935	QQR0582-001Z	FERRITE BEADS	
K937	QQR0582-001Z	FERRITE BEADS	
△ PC921	TLP421F/D4-GR/	IC (PHOTO COUPLE	
△ RY951	QSK0085-001	RELAY	
△ OR	QSK0130-001	RELAY	
△ OR	QSK0086-001	RELAY	
△ TH901	QAD0132-3R0	P THERMISTOR	
T111	QQR0907-001	IF TRANSFORMER	

Symbol No.	Part No.	Part Name	Description
△ T501	CE42034-002	HOR DRIVE TRANS	
△ T502	QOH0125-001	FB TRANSF	
△ T921	QOS0152-001	SW TRANSF	
△ T951	QOT0355-001	POWER TRANSF	
OR	QOT0372-001	POWER TRANSF	
△ FC901	CEM002-001Z	FUSE CLIP	
J601	QNN0349-002	PIN JACK	
J602	QNN0349-002	PIN JACK, 803Y	
J810	QNS0001-001	JACK	
△ LF901	QQR1159-001	LINE FILTER	
△ LF902	QQR0527-004	LINE FILTER	
△ VA901	ERZV10V621CS	ZNR	
△ CN001	QGB1505J1-35	B TO B CONNE	
△ CN002	QGB1505J1-25	B TO B CONNE	
△ CN003	QGB1505J1-15	B TO B CONNE	
△ CN004	QGA2501C5-07Z	W TO B CONNE	
△ CN005	QGA2501C5-06Z	W TO B CONNE	
△ CN007	QGA2501C5-06Z	W TO B CONNE	
△ CP932	ICP-N70-T	CIRCUIT PROTECTOR	
△ CP933	ICP-N70-T	CIRCUIT PROTECTOR	
△ CP936	ICP-N70-T	CIRCUIT PROTECTOR	
△ F901	QMF51U1-5R0-J8	FUSE	5.0A
△ F905	QMF2049-5R0Z-E	FUSE	5.0A
Y201	NRS463J-0R0X	MG R	0.0Ω 1/16W J, 803Y

DAF P.W. BOARD ASS'Y (SGJ-2003A-M2)

Symbol No.	Part No.	Part Name	Description
Q2751	2SD601A/QR/-X	TRANSISTOR	
Q2752	2SD601A/QR/-X	TRANSISTOR	
Q2753	2SC463Z	PNP TRANSISTOR	
D2761	ES1F-LFG2	DIODE	
D2762	ES1F-LFG2	DIODE	
D2771	MTZJ33A	ZENER DIODE	
R2701	QRG01GJ-220	OM R	22Ω 1W J
R2702	QRE121J-123Y	C R	12kΩ 1/2W J
R2708	QRZ0056-103Z	COMP R	10kΩ 1/2W K
R2751	NRS463J-473X	MG R	47kΩ 1/16W J
R2752	NRS463J-822X	MG R	8.2kΩ 1/16W J
R2753	NRS463J-122X	MG R	1.2kΩ 1/16W J
R2754	NRS463J-103X	MG R	10kΩ 1/16W J
R2755	NRS463J-563X	MG R	56kΩ 1/16W J
R2756	NRS463J-123X	MG R	12kΩ 1/16W J
R2757	NRS463J-472X	MG R	4.7kΩ 1/16W J
R2758	NRS463J-124X	MG R	120kΩ 1/16W J
R2761	QRE121J-184Y	C R	180kΩ 1/2W J
R2762	QRE121J-184Y	C R	180kΩ 1/2W J
R2763	QRE121J-184Y	C R	180kΩ 1/2W J
R2764	QRE121J-184Y	C R	180kΩ 1/2W J
R2765	QRE121J-184Y	C R	180kΩ 1/2W J
R2771	QRL089J-223	OM R	22kΩ 3W J
C2701	QFV71HJ-104	MF CAP.	0.1uF 50V J
C2751	QFLCHJ-333Z	M CAP.	0.033uF 50V J
C2752	QETNLEM-476	E CAP.	47uF 25V M
C2753	QFZ0122-103	MPP CAP.	0.01uF1.8kVH±3%
C2761	QFZ0122-682	MPP CAP.	6800pF1.8kVH±3%
C2771	QETNLM-106	E CAP.	10uF 50V M
L2701	QQL2028-272	COIL	
T2701	QQR1153-001	DEF TRANSF	

AV-32F703
AV-32F713
AV-32F803

CRT SOCKET P.W. BOARD ASS'Y
(SGJ-3004A-M2)

△ Symbol No.	Part No.	Part Name	Description
Q3108	2SA93AS/QR/-T	TRANSISTOR	
Q3109	2SC1740S/QR/-T	TRANSISTOR	
Q3106	2SA93AS/QR/-T	TRANSISTOR	
Q3107	2SA1964/DE/	POW TRANSISTOR	
Q3108	2SC5248/DE/	POW TRANSISTOR	
Q3109	2SC1740S/QR/-T	TRANSISTOR	
Q3151	2SC1740S/QR/-T	TRANSISTOR	
Q3152	2SA93AS/QR/-T	TRANSISTOR	
Q3301	2SC5083/L-P/-T	TRANSISTOR	
Q3302	2SC5083/L-P/-T	TRANSISTOR	
Q3303	2SC5083/L-P/-T	TRANSISTOR	
Q3304	2SC5147/CDE/F43	POW TRANSISTOR	
Q3305	2SC5147/CDE/F43	POW TRANSISTOR	
Q3306	2SC5147/CDE/F43	POW TRANSISTOR	
Q3351	2SA93AS/QR/-T	TRANSISTOR	
D3101	1SS133	DIODE	
D3105	RH15-T3	DIODE	
D3106	RH15-T3	DIODE	
D3301	1SS133	DIODE	
D3302	1SS133	DIODE	
D3303	1SS133	DIODE	
D3304	1SS82	DIODE	
D3305	1SS82	DIODE	
D3306	1SS82	DIODE	
D3311	MTZJ3. 6B	ZENER DIODE	
D3312	1SS133	DIODE	
D3313	MTZJ4. 3A	ZENER DIODE	
D3314	1SS133	DIODE	
D3331	1SS133	DIODE	
D3351	1SS133	DIODE	
D3352	1SS133	DIODE	
D3353	1SS133	DIODE	
D3354	1SS133	DIODE	
D3361	RM2C-LFA1	DIODE	
R3108	NRSAG3J-0ROX	MG R	0.0Ω 1/16W J
R3111	NRSAG3J-332X	MG R	3.3kΩ 1/16W J
R3114	QRJ146J-100X	C R	10Ω 1/4W J
R3115	NRSAG3J-470X	MG R	47Ω 1/16W J
R3116	NRSAG3J-470X	MG R	47Ω 1/16W J
R3117	NRSAG3J-102X	MG R	1kΩ 1/16W J
R3119	NRSAG3J-121X	MG R	120Ω 1/16W J
△ R3122	QRZ9021-561	F R	560 Ω 1W J
R3123	NRSAG3J-122X	MG R	1.2kΩ 1/16W J
R3124	NRSAG3J-390X	MG R	39Ω 1/16W J
R3125	NRSAG3J-5R6X	MG R	5.6Ω 1/16W J
R3126	NRSAG3J-563X	MG R	56kΩ 1/16W J
R3127	NRSAG3J-563X	MG R	56kΩ 1/16W J
R3128	NRSAG3J-122X	MG R	1.2kΩ 1/16W J
R3129	NRSAG3J-5R6X	MG R	5.6Ω 1/16W J
R3130	NRSAG3J-390X	MG R	39Ω 1/16W J
R3131	NRSAG3J-121X	MG R	120Ω 1/16W J
R3132	QRL029J-391	OM R	390Ω 2W J
R3134	NRSAG3J-222X	MG R	2.2kΩ 1/16W J
R3136	NRSAG3J-333X	MG R	33kΩ 1/16W J
R3139	NRSAG3J-681X	MG R	680Ω 1/16W J
R3142	NRSAG3J-124X	MG R	120kΩ 1/16W J
R3143	NRSAG3J-681X	MG R	680Ω 1/16W J
R3145	NRSAG3J-5R6X	MG R	5.6Ω 1/16W J
R3146	NRSAG3J-5R6X	MG R	5.6Ω 1/16W J
R3151	NRSAG3J-473X	MG R	47kΩ 1/16W J
R3152	NRSAG3J-683X	MG R	68kΩ 1/16W J
R3153	NRSAG3J-683X	MG R	68kΩ 1/16W J
R3154	NRSAG3J-473X	MG R	47kΩ 1/16W J
R3301	NRSAG3J-151X	MG R	150Ω 1/16W J
R3302	NRSAG3J-151X	MG R	150Ω 1/16W J
R3303	NRSAG3J-151X	MG R	150Ω 1/16W J
R3304	NRSAG3J-121X	MG R	120Ω 1/16W J
R3305	NRSAG3J-121X	MG R	120Ω 1/16W J
R3306	NRSAG3J-121X	MG R	120Ω 1/16W J
R3307	NRSAG3J-470X	MG R	47Ω 1/16W J
R3308	NRSAG3J-470X	MG R	47Ω 1/16W J
R3309	NRSAG3J-470X	MG R	47Ω 1/16W J
R3310	QRG029J-153	OM R	15kΩ 2W J
R3311	QRG029J-153	OM R	15kΩ 2W J
R3312	QRG029J-153	OM R	15kΩ 2W J
R3313	QRG029J-183	OM R	18kΩ 2W J
R3314	QRG029J-183	OM R	18kΩ 2W J
R3315	QRG029J-183	OM R	18kΩ 2W J
R3316	NRSAG3J-0ROX	MG R	0.0Ω 1/16W J
R3317	NRSAG3J-0ROX	MG R	0.0Ω 1/16W J
R3318	NRSAG3J-0ROX	MG R	0.0Ω 1/16W J

△ Symbol No.	Part No.	Part Name	Description
R3325	QRC121K-102Z	MF R	1kΩ 1/2W K
R3326	QRC121K-102Z	MF R	1kΩ 1/2W K
R3327	QRC121K-102Z	MF R	1kΩ 1/2W K
R3331	NRSAG3J-272X	MG R	2.7kΩ 1/16W J
R3332	NRSAG3J-272X	MG R	2.7kΩ 1/16W J
R3333	NRSAG3J-272X	MG R	2.7kΩ 1/16W J
R3334	NRSAG3J-152X	MG R	1.5kΩ 1/16W J
R3335	NRSAG3J-271X	MG R	270Ω 1/16W J
R3336	NRSAG3J-0ROX	MG R	0.0Ω 1/16W J
R3337	NRSAG3J-0ROX	MG R	0.0Ω 1/16W J
R3338	NRSAG3J-0ROX	MG R	0.0Ω 1/16W J
R3351	NRSAG3J-102X	MG R	1kΩ 1/16W J
R3352	NRSAG3J-102X	MG R	1kΩ 1/16W J
R3353	NRSAG3J-102X	MG R	1kΩ 1/16W J
R3354	NRSAG3J-561X	MG R	560Ω 1/16W J
R3355	NRSAG3J-563X	MG R	56kΩ 1/16W J
R3361	QRC121K-105Z	MF R	1MΩ 1/2W K
R3362	QRC121K-102Z	MF R	1kΩ 1/2W K
R3363	QRC121K-474Z	MF R	470kΩ 1/2W K
C3101	QETN1HM-106	E CAP.	10μF 50V M
C3109	QETN1CM-107	E CAP.	100μF 16V M
C3110	NDC31HJ-221X	C CAP.	220pF 50V J
C3111	NDC31HJ-221X	C CAP.	220pF 50V J
C3113	QETN2CM-106	E CAP.	10μF 160V M
C3114	QCB32HK-472	C CAP.	4700pF 500V K
C3115	QCB32HK-472	C CAP.	4700pF 500V K
C3117	QETN2CM-106	E CAP.	10μF 160V M
C3118	QETN0JM-107	E CAP.	100μF 6.3V M
C3119	QETN1AM-107	E CAP.	100μF 10V M
C3120	QETN1AM-337	E CAP.	330μF 10V M
C3121	QCS32HJ-151	C CAP.	150pF 500V J
C3122	NDC31HJ-5R0X	C CAP.	5.0pF 50V J
C3125	NRSAG3J-0ROX	MG R	0.0Ω 1/16W J
C3151	NCB21EK-104X	C CAP.	0.1μF 25V K
C3152	NCB21EK-104X	C CAP.	0.1μF 25V K
C3301	NDC31HJ-561X	C CAP.	560pF 50V J
C3302	NDC31HJ-391X	C CAP.	390pF 50V J
C3303	NDC31HJ-561X	C CAP.	560pF 50V J
C3321	QETN2EM-105	E CAP.	1μF 250V M
C3322	QETN2EM-105	E CAP.	1μF 250V M
C3323	QETN1CM-477	E CAP.	470μF 16V M
C3351	QETN1CM-337	E CAP.	330μF 16V M
C3361	QETN2EM-105	E CAP.	1μF 250V M
C3362	QUY153-050Y	IM BUS WIRE	
C3363	QCZ0824-102	C CAP.	100pF 3kV P
L3301	QQL244K-180Z	COIL	18μH K
L3302	QQL244K-180Z	COIL	18μH K
L3303	QQL244K-180Z	COIL	18μH K
L3304	QQL244K-470Z	COIL	47μH K
L3305	QQL244K-470Z	COIL	47μH K
L3306	QQL244K-470Z	COIL	47μH K
K3102	CE41492-001Z	COIL	
K3103	CE41492-001Z	COIL	
K3104	CE41492-001Z	COIL	
K3105	CE41492-001Z	COIL	
△ SK3001	CE42670-001	CRT SOCKET	
CN3004	QJB003-074022	SIN ID C-B WIRE	
CN3005	WJA0029-002A	E-S ID WIRE	

PIP P.W. BOARD ASS'Y
(SGJ-4001A-M2) [AV-32F803/Y ONLY]

△ Symbol No.	Part No.	Part Name	Description
SF4101	QAX0726-001	SAW FILTER	
TU4001	QAU0273-001	TUNER	
IC4101	M523425P	IC	
IC4301	SDA9889X	IC	
Q4101	2SC5083/L-P/-T	TRANSISTOR	
Q4131	2SB709A/QR/-X	TRANSISTOR	
Q4301	2SD601A/QR/-X	TRANSISTOR	

△ Symbol No.	Part No.	Part Name	Description
Q4302	2SD601A/QR/-X	TRANSISTOR	
Q4303	2SD601A/QR/-X	TRANSISTOR	
Q4331	2SB709A/QR/-X	TRANSISTOR	
Q4332	2SB709A/QR/-X	TRANSISTOR	
Q4333	2SB709A/QR/-X	TRANSISTOR	
D4301	1SS133	DIODE	
R4001	NRS463J-103X	MG R	10kΩ 1/16W J
R4002	NRS463J-103X	MG R	10kΩ 1/16W J
R4003	NRS463J-101X	MG R	100Ω 1/16W J
R4004	NRS463J-101X	MG R	100Ω 1/16W J
R4005	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R4008	NRS463J-820X	MG R	82Ω 1/16W J
R4101	NRS463J-562X	MG R	5.6kΩ 1/16W J
R4102	NRS463J-182X	MG R	1.8kΩ 1/16W J
R4103	QRE121J-101Y	C R	100Ω 1/2W J
R4104	NRS463J-180X	MG R	18Ω 1/16W J
R4105	NRS463J-270X	MG R	27Ω 1/16W J
R4111	NRS463J-224X	MG R	220kΩ 1/16W J
R4113	NRS463J-101X	MG R	100Ω 1/16W J
R4114	NRS463J-331X	MG R	330Ω 1/16W J
R4115	NRS463J-101X	MG R	100Ω 1/16W J
R4116	NRS463J-680X	MG R	68Ω 1/16W J
R4117	NRS463J-273X	MG R	27kΩ 1/16W J
R4118	NRS463J-223X	MG R	22kΩ 1/16W J
R4120	NRS463J-273X	MG R	27kΩ 1/16W J
R4121	NRS463J-103X	MG R	10kΩ 1/16W J
R4131	NRS463J-102X	MG R	1kΩ 1/16W J
R4132	NRS463J-331X	MG R	330Ω 1/16W J
R4133	NRS463J-821X	MG R	820Ω 1/16W J
R4134	NRS463J-561X	MG R	560Ω 1/16W J
R4135	NRS463J-102X	MG R	1kΩ 1/16W J
R4161	NRS463J-332X	MG R	3.3kΩ 1/16W J
R4163	NRS463J-223X	MG R	22kΩ 1/16W J
R4171	NRS463J-103X	MG R	10kΩ 1/16W J
R4301	NRS463J-473X	MG R	47kΩ 1/16W J
R4302	NRS463J-223X	MG R	22kΩ 1/16W J
R4303	NRS463J-222X	MG R	2.2kΩ 1/16W J
R4304	NRS463J-473X	MG R	47kΩ 1/16W J
R4305	NRS463J-223X	MG R	22kΩ 1/16W J
R4306	NRS463J-222X	MG R	2.2kΩ 1/16W J
R4307	NRS463J-332X	MG R	3.3kΩ 1/16W J
R4308	NRS463J-332X	MG R	3.3kΩ 1/16W J
R4309	NRS463J-102X	MG R	1kΩ 1/16W J
R4311	NRS463J-101X	MG R	100Ω 1/16W J
R4313	NRS463J-101X	MG R	100Ω 1/16W J
R4314	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R4316	NRS463J-331X	MG R	330Ω 1/16W J
R4317	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R4331	NRS463J-221X	MG R	220Ω 1/16W J
R4332	NRS463J-102X	MG R	1kΩ 1/16W J
R4337	NRS463J-221X	MG R	220Ω 1/16W J
R4338	NRS463J-102X	MG R	1kΩ 1/16W J
R4343	NRS463J-221X	MG R	220Ω 1/16W J
R4344	NRS463J-102X	MG R	1kΩ 1/16W J
C4001	QETN1HM-475	E CAP.	4.7μF 50V M
C4003	QETN1HM-106	E CAP.	10μF 50V M
C4004	QETN1QM-107	E CAP.	100μF 16V M
C4006	QETN1EM-476	E CAP.	47μF 25V M
C4101	NCB31HK-103X	C CAP.	0.01μF 50V K
C4102	NCB31HK-103X	C CAP.	0.01μF 50V K
C4104	NCB31HK-103X	C CAP.	0.01μF 50V K
C4105	NCB31HK-103X	C CAP.	0.01μF 50V K
C4106	QETN1EM-476	E CAP.	47μF 25V M
C4107	NCB31HK-103X	C CAP.	0.01μF 50V K
C4113	NCB31HK-103X	C CAP.	0.01μF 50V K
C4114	NCB31HK-103X	C CAP.	0.01μF 50V K
C4116	QFV1HJ-224Z	MF CAP.	0.22μF 50V J
C4117	QETN1EM-476	E CAP.	47μF 25V M
C4118	NCB31HK-103X	C CAP.	0.01μF 50V K
C4119	NDC31HJ-681X	C CAP.	680pF 50V J
C4120	QETN1HM-474	E CAP.	0.47μF 50V M
C4124	NCB31HK-103X	C CAP.	0.01μF 50V K
C4131	NCB31HK-103X	C CAP.	0.01μF 50V K
C4132	NDC31HJ-181X	C CAP.	180pF 50V J
C4161	QETN1HM-106	E CAP.	10μF 50V M
C4168	NCB31HK-103X	C CAP.	0.01μF 50V K
C4301	NRS463J-0R0X	MG R	0.0Ω 1/16W J
C4302	NRS463J-0R0X	MG R	0.0Ω 1/16W J
C4312	NDC31HJ-270X	C CAP.	27pF 50V J
C4313	NDC31HJ-270X	C CAP.	27pF 50V J

△ Symbol No.	Part No.	Part Name	Description
C4314	QETN1HM-106	E CAP.	10μF 50V M
C4315	NCB31HK-103X	C CAP.	0.01μF 50V K
C4316	NCB31HK-103X	C CAP.	0.01μF 50V K
C4317	NCB31HK-103X	C CAP.	0.01μF 50V K
C4318	NCB31HK-103X	C CAP.	0.01μF 50V K
C4319	QETN1HM-106	E CAP.	10μF 50V M
C4320	NCB31HK-103X	C CAP.	0.01μF 50V K
C4321	QETN1HM-105	E CAP.	1μF 50V M
C4322	NCB31HK-103X	C CAP.	0.01μF 50V K
C4323	QETN1HM-106	E CAP.	10μF 50V M
C4324	NCB31HK-103X	C CAP.	0.01μF 50V K
C4325	NCB31HK-103X	C CAP.	0.01μF 50V K
C4326	NCB31EK-104X	C CAP.	0.1μF 25V K
C4327	QETN1HM-225	E CAP.	2.2μF 50V M
C4328	NCB31HK-103X	C CAP.	0.01μF 50V K
C4329	QETN1HM-225	E CAP.	2.2μF 50V M
C4330	NCB31HK-103X	C CAP.	0.01μF 50V K
C4331	NCB31EK-104X	C CAP.	0.1μF 25V K
L4001	QQL244K-560Z	COIL	56μH K
L4101	QQL2014-R22	COIL	
L4113	QQL244K-4R7Z	COIL	4.7μH K
L4131	QQL244K-150Z	COIL	15μH K
L4302	QQL244J-6R8Z	COIL	6.8μH J
L4303	QQL244J-6R8Z	COIL	6.8μH J
L4304	QQL244J-6R8Z	COIL	6.8μH J
CF4131	QAX0639-001Z	C TRAP	
X4301	QAX0521-001Z	CRYSTAL RESONATOR	
T4111	QQR0907-001	IF TRANSFORMER	
CN4002	QGB1505K1-25	B TO B CONNE	

AV SEL P.W. BOARD ASS'Y
(SGJ-5001A-M2) [AV-32F803/Y]

△ Symbol No.	Part No.	Part Name	Description
IC5001	CXA2134Q	IC	
IC5151	NJM2150AD	IC	
IC5301	PQ3R013	IC	
IC5501	TA1218AN	IC	
Q5001	2SB709A/QR/-X	TRANSISTOR	
Q5002	2SB709A/QR/-X	TRANSISTOR	
Q5384	DTC323TK	DIGI TRANSISTOR	
Q5385	DTC323TK	DIGI TRANSISTOR	
Q5386	DTC323TK	DIGI TRANSISTOR	
Q5387	DTC323TK	DIGI TRANSISTOR	
Q5501	2SB709A/QR/-X	TRANSISTOR	
D5391	MTZJ9.1C	ZENER DIODE	
D5392	MTZJ9.1C	ZENER DIODE	
D5501	MTZJ9.1C	ZENER DIODE	
D5502	MTZJ9.1C	ZENER DIODE	
D5503	MTZJ9.1C	ZENER DIODE	
D5504	MTZJ9.1C	ZENER DIODE	
D5505	MTZJ9.1C	ZENER DIODE	
D5507	MTZJ9.1C	ZENER DIODE	
D5508	MTZJ9.1C	ZENER DIODE	
D5509	MTZJ9.1C	ZENER DIODE	
D5510	MTZJ9.1C	ZENER DIODE	
D5511	MTZJ9.1C	ZENER DIODE	
D5512	MTZJ9.1C	ZENER DIODE	
D5513	MTZJ9.1C	ZENER DIODE	
D5514	MTZJ9.1C	ZENER DIODE	
D5515	MTZJ9.1C	ZENER DIODE	
R5001	NRS463J-105X	MG R	1MΩ 1/16W J
R5002	NRS463J-104X	MG R	100kΩ 1/16W J
R5003	NRS463J-682X	MG R	6.8kΩ 1/16W J
R5004	NRS463J-682X	MG R	6.8kΩ 1/16W J
R5005	NRS463F-623X	MG R	62kΩ 1/16W F
R5007	NRS463J-332X	MG R	3.3kΩ 1/16W J
R5008	NRS463J-302X	MG R	3kΩ 1/16W J
R5010	NRS463J-392X	MG R	3.9kΩ 1/16W J
R5011	NRS463J-221X	MG R	22Ω 1/16W J
R5012	NRS463J-221X	MG R	22Ω 1/16W J

AV-32F703
AV-32F713
AV-32F803

△ Symbol No.	Part No.	Part Name	Description
R5031	NRSA63J-101X	MG R	100Ω 1/16W J
R5032	NRSA63J-101X	MG R	100Ω 1/16W J
R5033	NRSA63J-272X	MG R	2.7kΩ 1/16W J
R5034	NRSA63J-272X	MG R	2.7kΩ 1/16W J
R5151	NRSA63J-223X	MG R	22kΩ 1/16W J
R5152	NRSA63J-223X	MG R	22kΩ 1/16W J
R5153	NRSA63J-223X	MG R	22kΩ 1/16W J
R5154	NRSA63J-223X	MG R	22kΩ 1/16W J
R5155	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5157	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5159	NRSA63J-103X	MG R	10kΩ 1/16W J
R5301	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5302	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5384	NRSA63J-223X	MG R	22kΩ 1/16W J
R5385	NRSA63J-223X	MG R	22kΩ 1/16W J
R5386	NRSA63J-223X	MG R	22kΩ 1/16W J
R5387	NRSA63J-223X	MG R	22kΩ 1/16W J
R5391	NRSA63J-221X	MG R	220Ω 1/16W J
R5392	NRSA63J-221X	MG R	220Ω 1/16W J
R5393	NRSA63J-823X	MG R	82kΩ 1/16W J
R5394	NRSA63J-823X	MG R	82kΩ 1/16W J
R5395	NRSA63J-221X	MG R	220Ω 1/16W J
R5396	NRSA63J-221X	MG R	220Ω 1/16W J
R5501	NRSA63J-221X	MG R	220Ω 1/16W J
R5502	NRSA63J-221X	MG R	220Ω 1/16W J
R5503	NRSA63J-221X	MG R	220Ω 1/16W J
R5504	NRSA63J-221X	MG R	220Ω 1/16W J
R5505	NRSA63J-221X	MG R	220Ω 1/16W J
R5507	NRSA63J-103X	MG R	10kΩ 1/16W J
R5508	NRSA63J-153X	MG R	15kΩ 1/16W J
R5509	NRSA63J-221X	MG R	220Ω 1/16W J
R5510	NRSA63J-221X	MG R	220Ω 1/16W J
R5511	NRSA63J-221X	MG R	220Ω 1/16W J
R5512	NRSA63J-221X	MG R	220Ω 1/16W J
R5513	NRSA63J-153X	MG R	15kΩ 1/16W J
R5514	NRSA63J-103X	MG R	10kΩ 1/16W J
R5515	NRSA63J-103X	MG R	10kΩ 1/16W J
R5516	NRSA63J-103X	MG R	10kΩ 1/16W J
R5517	NRSA63J-103X	MG R	10kΩ 1/16W J
R5519	NRSA63J-750X	MG R	75Ω 1/16W J
R5520	NRSA63J-750X	MG R	75Ω 1/16W J
R5521	NRSA63J-750X	MG R	75Ω 1/16W J
R5522	NRSA63J-224X	MG R	220kΩ 1/16W J
R5523	NRSA63J-224X	MG R	220kΩ 1/16W J
R5524	NRSA63J-103X	MG R	10kΩ 1/16W J
R5526	NRSA63J-103X	MG R	10kΩ 1/16W J
R5527	NRSA63J-750X	MG R	75Ω 1/16W J
R5532	NRSA63J-224X	MG R	220kΩ 1/16W J
R5533	NRSA63J-224X	MG R	220kΩ 1/16W J
R5541	NRSA63J-221X	MG R	220Ω 1/16W J
R5542	NRSA63J-221X	MG R	220Ω 1/16W J
R5543	NRSA63J-221X	MG R	220Ω 1/16W J
R5544	NRSA63J-331X	MG R	330Ω 1/16W J
R5545	NRSA63J-331X	MG R	330Ω 1/16W J
R5546	NRSA63J-103X	MG R	10kΩ 1/16W J
R5538	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5539	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5560	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5561	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5564	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5565	NRSA63J-0R0X	MG R	0.0Ω 1/16W J
R5566	NRSA63J-224X	MG R	220kΩ 1/16W J
R5567	NRSA63J-224X	MG R	220kΩ 1/16W J
R5568	NRSA63J-221X	MG R	220Ω 1/16W J
R5569	NRSA63J-221X	MG R	220Ω 1/16W J
C5001	QENCLHM-475	E CAP.	4.7μF 50V M
C5002	NCB31HK-562X	C CAP.	5600pF 50V K
C5003	NCB31HK-123X	C CAP.	0.012μF 50V K
C5004	QETNLHM-105	E CAP.	1μF 50V M
C5005	QETNLHM-475	E CAP.	4.7μF 50V M
C5006	QETNLHM-106	E CAP.	10μF 50V M
C5007	QETNLHM-475	E CAP.	4.7μF 50V M
C5008	QETNLHM-107	E CAP.	100μF 16V M
C5009	QENCLHM-475	E CAP.	4.7μF 50V M
C5010	QETNLHM-475	E CAP.	4.7μF 50V M
C5011	QENCLHM-475	E CAP.	4.7μF 50V M
C5012	NCB31HK-272X	C CAP.	2700pF 50V K
C5013	NCB31HK-473X	C CAP.	0.047μF 50V K
C5014	QENCLHM-475	E CAP.	4.7μF 50V M

△ Symbol No.	Part No.	Part Name	Description
C5015	QBTCLCK-106Z	TAN.CAP.	10μF 16V K
C5016	QETNLHM-105	E CAP.	1μF 50V M
C5017	QENCLHM-105	E CAP.	1μF 50V M
C5018	QENCLHM-105	E CAP.	1μF 50V M
C5019	NCB31HK-223X	C CAP.	0.022μF 50V K
C5020	NCB31HK-472X	C CAP.	4700pF 50V K
C5021	QENCLHM-475	E CAP.	4.7μF 50V M
C5022	NCB31EK-104X	C CAP.	0.1μF 25V K
C5023	NCB31HK-472X	C CAP.	4700pF 50V K
C5024	QENCLHM-475	E CAP.	4.7μF 50V M
C5025	NCB31EK-104X	C CAP.	0.1μF 25V K
C5026	QBTCLCK-335Z	TAN.CAP.	3.3μF 16V K
C5031	QETNLHM-106	E CAP.	10μF 50V M
C5151	QENCLHM-105	E CAP.	1μF 50V M
C5152	QENCLHM-105	E CAP.	1μF 50V M
C5153	NCB31HK-332X	C CAP.	3300pF 50V K
C5154	NCB31HK-332X	C CAP.	3300pF 50V K
C5155	NCB31EK-333X	C CAP.	0.033μF 25V K
C5156	NCB31EK-333X	C CAP.	0.033μF 25V K
C5157	QETNLHM-106	E CAP.	10μF 50V M
C5158	QETNLHM-106	E CAP.	10μF 50V M
C5159	QETNLEM-476	E CAP.	47μF 25V M
C5160	NCB31EK-104X	C CAP.	0.1μF 25V K
C5301	QETNLEM-476	E CAP.	47μF 25V M
C5302	QETNLAM-227	E CAP.	220μF 10V M
C5391	QETNLHM-474	E CAP.	0.47μF 50V M
C5392	QETNLHM-474	E CAP.	0.47μF 50V M
C5501	QETNLHM-225	E CAP.	2.2μF 50V M
C5502	QETNLHM-225	E CAP.	2.2μF 50V M
C5503	QETNLHM-106	E CAP.	10μF 50V M
C5504	QENCLCM-106	E CAP.	10μF 16V M
C5506	QETNLHM-106	E CAP.	10μF 50V M
C5508	QETNLHM-106	E CAP.	10μF 50V M
C5509	NCB31HK-103X	C CAP.	0.01μF 50V K
C5520	QETNLHM-225	E CAP.	2.2μF 50V M
C5521	QETNLHM-225	E CAP.	2.2μF 50V M
C5531	NCB31HK-103X	C CAP.	0.01μF 50V K
C5532	QETNLEM-476	E CAP.	47μF 25V M
C5533	NCB31HK-103X	C CAP.	0.01μF 50V K
C5534	QENCLCM-106	E CAP.	10μF 16V M
C5544	QETNLHM-225	E CAP.	2.2μF 50V M
C5545	QETNLHM-225	E CAP.	2.2μF 50V M
J5501	QNZ0454-001	AV JACK	
J5502	QNN0349-001	PIN JACK	
J5503	QNN0348-001	PIN JACK	
J5504	QNN0348-001	PIN JACK	
CN5001	QGC2505C2-38	CARD EDGE CONNE	
CN5001	QGB1505K1-35	B TO B CONNE	
CN5003	QGB1505K1-15	B TO B CONNE	
CN5006	QGA2501C5-05Z	W TO B CONNE	

AV SEL P.W. BOARD ASS'Y
(SGJ-5002A-M2) [AV-32F703 γ] [AV-32F713 γ]

△ Symbol No.	Part No.	Part Name	Description
IC5001	CXA2134Q	IC	
IC5151	NJM2150AD	IC	
IC5201	TC90A49P	IC	
IC5501	TA1218AN	IC	
Q5001	2SB709A/QR/-X	TRANSISTOR	
Q5002	2SB709A/QR/-X	TRANSISTOR	
Q5211	2SD601A/QR/-X	TRANSISTOR	
Q5212	2SD601A/QR/-X	TRANSISTOR	
Q5251	2SD601A/QR/-X	TRANSISTOR	
Q5252	2SB709A/QR/-X	TRANSISTOR	
Q5253	2SB709A/QR/-X	TRANSISTOR	
Q5261	2SB709A/QR/-X	TRANSISTOR	
Q5262	2SD601A/QR/-X	TRANSISTOR	
Q5263	2SB709A/QR/-X	TRANSISTOR	

△ Symbol No.	Part No.	Part Name	Description	△ Symbol No.	Part No.	Part Name	Description
Q5384	DTC323TK	DIGI TRANSISTOR		R5509	NRS463J-221X	MG R	220Ω 1/16W J
Q5385	DTC323TK	DIGI TRANSISTOR		R5510	NRS463J-221X	MG R	220Ω 1/16W J
Q5386	DTC323TK	DIGI TRANSISTOR		R5511	NRS463J-221X	MG R	220Ω 1/16W J
Q5387	DTC323TK	DIGI TRANSISTOR		R5512	NRS463J-221X	MG R	220Ω 1/16W J
Q5501	2SB709A/QR/-X	TRANSISTOR		R5513	NRS463J-153X	MG R	15kΩ 1/16W J
D5391	MTZJ9.1C	ZENER DIODE		R5514	NRS463J-103X	MG R	10kΩ 1/16W J
D5392	MTZJ9.1C	ZENER DIODE		R5515	NRS463J-103X	MG R	10kΩ 1/16W J
D5501	MTZJ9.1C	ZENER DIODE		R5516	NRS463J-103X	MG R	10kΩ 1/16W J
D5502	MTZJ9.1C	ZENER DIODE		R5517	NRS463J-103X	MG R	10kΩ 1/16W J
D5503	MTZJ9.1C	ZENER DIODE		R5519	NRS463J-750X	MG R	75Ω 1/16W J
D5504	MTZJ9.1C	ZENER DIODE		R5520	NRS463J-750X	MG R	75Ω 1/16W J
D5505	MTZJ9.1C	ZENER DIODE		R5521	NRS463J-750X	MG R	75Ω 1/16W J
D5507	MTZJ9.1C	ZENER DIODE		R5522	NRS463J-224X	MG R	220kΩ 1/16W J
D5508	MTZJ9.1C	ZENER DIODE		R5523	NRS463J-224X	MG R	220kΩ 1/16W J
D5509	MTZJ9.1C	ZENER DIODE		R5524	NRS463J-103X	MG R	10kΩ 1/16W J
D5510	MTZJ9.1C	ZENER DIODE		R5526	NRS463J-103X	MG R	10kΩ 1/16W J
D5511	MTZJ9.1C	ZENER DIODE		R5527	NRS463J-750X	MG R	75Ω 1/16W J
D5512	MTZJ9.1C	ZENER DIODE		R5532	NRS463J-224X	MG R	220kΩ 1/16W J
D5513	MTZJ9.1C	ZENER DIODE		R5533	NRS463J-224X	MG R	220kΩ 1/16W J
R5001	NRS463J-105X	MG R	1MΩ 1/16W J	R5541	NRS463J-221X	MG R	220Ω 1/16W J
R5002	NRS463J-104X	MG R	100kΩ 1/16W J	R5542	NRS463J-221X	MG R	220Ω 1/16W J
R5003	NRS463J-682X	MG R	6.8kΩ 1/16W J	R5543	NRS463J-221X	MG R	220Ω 1/16W J
R5004	NRS463J-682X	MG R	6.8kΩ 1/16W J	R5544	NRS463J-221X	MG R	220Ω 1/16W J
R5005	NRS463F-623X	MG R	62kΩ 1/16W F	R5545	NRS463J-331X	MG R	33kΩ 1/16W J
R5007	NRS463J-332X	MG R	3.3kΩ 1/16W J	R5546	NRS463J-331X	MG R	33kΩ 1/16W J
R5008	NRS463J-302X	MG R	3kΩ 1/16W J	R5547	NRS463J-103X	MG R	10kΩ 1/16W J
R5010	NRS463J-392X	MG R	3.9kΩ 1/16W J	R5548	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R5011	NRS463J-221X	MG R	220Ω 1/16W J	R5549	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R5012	NRS463J-221X	MG R	220Ω 1/16W J	R5560	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R5031	NRS463J-101X	MG R	100Ω 1/16W J	R5561	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R5032	NRS463J-101X	MG R	100Ω 1/16W J	R5564	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R5033	NRS463J-272X	MG R	2.7kΩ 1/16W J	R5565	NRS463J-0R0X	MG R	0.0Ω 1/16W J
R5034	NRS463J-272X	MG R	2.7kΩ 1/16W J	C5001	QENC1HM-475	E CAP.	4.7μF 50V M
R5151	NRS463J-223X	MG R	22kΩ 1/16W J	C5002	NCB31HK-562X	C CAP.	5600pF 50V K
R5152	NRS463J-223X	MG R	22kΩ 1/16W J	C5003	NCB31HK-123X	C CAP.	0.012μF 50V K
R5153	NRS463J-223X	MG R	22kΩ 1/16W J	C5004	QETNLHM-105	E CAP.	1μF 50V M
R5154	NRS463J-223X	MG R	22kΩ 1/16W J	C5005	QETNLHM-475	E CAP.	4.7μF 50V M
R5155	NRS463J-0R0X	MG R	0.0Ω 1/16W J	C5006	QETNLHM-106	E CAP.	10μF 50V M
R5157	NRS463J-0R0X	MG R	0.0Ω 1/16W J	C5007	QETNLHM-475	E CAP.	4.7μF 50V M
R5159	NRS463J-103X	MG R	10kΩ 1/16W J	C5008	QETNLHM-107	E CAP.	100μF 16V M
R5210	NRS463J-0R0X	MG R	0.0Ω 1/16W J	C5009	QENC1HM-475	E CAP.	4.7μF 50V M
R5211	NRS463J-332X	MG R	3.3kΩ 1/16W J	C5010	QETNLHM-475	E CAP.	4.7μF 50V M
R5212	NRS463J-103X	MG R	10kΩ 1/16W J	C5011	QENC1HM-475	E CAP.	4.7μF 50V M
R5213	NRS463J-102X	MG R	1kΩ 1/16W J	C5012	NCB31HK-272X	C CAP.	2700pF 50V K
R5214	NRS463J-181X	MG R	180Ω 1/16W J	C5013	NCB31HK-473X	C CAP.	0.047μF 50V K
R5215	NRS463J-152X	MG R	1.5kΩ 1/16W J	C5014	QENC1HM-475	E CAP.	4.7μF 50V M
R5216	NRS463J-182X	MG R	1.8kΩ 1/16W J	C5015	QBTCLCK-106Z	TAN.CAP.	10μF 16V K
R5217	NRS463J-222X	MG R	2.2kΩ 1/16W J	C5016	QETNLHM-105	E CAP.	1μF 50V M
R5240	NRS463J-0R0X	MG R	0.0Ω 1/16W J	C5017	QENC1HM-105	E CAP.	1μF 50V M
R5241	NRS463J-821X	MG R	820Ω 1/16W J	C5018	QENC1HM-105	E CAP.	1μF 50V M
R5242	NRS463J-101X	MG R	100Ω 1/16W J	C5019	NCB31HK-223X	C CAP.	0.022μF 50V K
R5243	NRS463J-101X	MG R	100Ω 1/16W J	C5020	NCB31HK-472X	C CAP.	4700pF 50V K
R5251	NRS463J-471X	MG R	470Ω 1/16W J	C5021	QENC1HM-475	E CAP.	4.7μF 50V M
R5253	NRS463J-102X	MG R	1kΩ 1/16W J	C5022	NCB31EK-104X	C CAP.	0.1μF 25V K
R5254	NRS463J-102X	MG R	1kΩ 1/16W J	C5023	NCB31HK-472X	C CAP.	4700pF 50V K
R5255	NRS463J-681X	MG R	680Ω 1/16W J	C5024	QENC1HM-475	E CAP.	4.7μF 50V M
R5258	NRS463J-101X	MG R	100Ω 1/16W J	C5025	NCB31EK-104X	C CAP.	0.1μF 25V K
R5259	NRS463J-222X	MG R	2.2kΩ 1/16W J	C5026	QBTCLCK-335Z	TAN.CAP.	3.3μF 16V K
R5261	NRS463J-101X	MG R	100Ω 1/16W J	C5031	QETNLHM-106	E CAP.	10μF 50V M
R5262	NRS463J-222X	MG R	2.2kΩ 1/16W J	C5151	QENC1HM-105	E CAP.	1μF 50V M
R5263	NRS463J-471X	MG R	470Ω 1/16W J	C5152	QENC1HM-105	E CAP.	1μF 50V M
R5265	NRS463J-102X	MG R	1kΩ 1/16W J	C5153	NCB31HK-332X	C CAP.	3300pF 50V K
R5269	NRS463J-681X	MG R	680Ω 1/16W J	C5154	NCB31HK-332X	C CAP.	3300pF 50V K
R5270	NRS463J-102X	MG R	1kΩ 1/16W J	C5155	NCB31EK-333X	C CAP.	0.033μF 25V K
R5384	NRS463J-223X	MG R	22kΩ 1/16W J	C5156	NCB31EK-333X	C CAP.	0.033μF 25V K
R5385	NRS463J-223X	MG R	22kΩ 1/16W J	C5157	QETNLHM-106	E CAP.	10μF 50V M
R5386	NRS463J-223X	MG R	22kΩ 1/16W J	C5158	QETNLHM-106	E CAP.	10μF 50V M
R5387	NRS463J-223X	MG R	22kΩ 1/16W J	C5159	QETNLEM-476	E CAP.	47μF 25V M
R5391	NRS463J-221X	MG R	220Ω 1/16W J	C5160	NCB31EK-104X	C CAP.	0.1μF 25V K
R5392	NRS463J-221X	MG R	220Ω 1/16W J	C5208	QETNLEM-476	E CAP.	47μF 25V M
R5393	NRS463J-823X	MG R	82kΩ 1/16W J	C5209	NCB31HK-103X	C CAP.	0.01μF 50V K
R5394	NRS463J-823X	MG R	82kΩ 1/16W J	C5205	QETNLEM-476	E CAP.	47μF 25V M
R5395	NRS463J-221X	MG R	220Ω 1/16W J	C5206	NCB31HK-103X	C CAP.	0.01μF 50V K
R5396	NRS463J-221X	MG R	220Ω 1/16W J	C5211	QENC1CM-106	E CAP.	10μF 16V M
R5501	NRS463J-221X	MG R	220Ω 1/16W J	C5212	NDC31HJ-101X	C CAP.	100pF 50V J
R5502	NRS463J-221X	MG R	220Ω 1/16W J	C5213	NDC31HJ-470X	C CAP.	470pF 50V J
R5503	NRS463J-221X	MG R	220Ω 1/16W J	C5214	NDC31HJ-181X	C CAP.	180pF 50V J
R5504	NRS463J-221X	MG R	220Ω 1/16W J	C5215	QETNLHM-474	E CAP.	0.47μF 50V M
R5505	NRS463J-221X	MG R	220Ω 1/16W J	C5226	NCB31HK-103X	C CAP.	0.01μF 50V K
R5507	NRS463J-103X	MG R	10kΩ 1/16W J	C5231	QETNLCM-107	E CAP.	100μF 16V M
R5508	NRS463J-153X	MG R	15kΩ 1/16W J	C5232	NCB31HK-103X	C CAP.	0.01μF 50V K

AV-32F703
AV-32F713
AV-32F803

△ Symbol No.	Part No.	Part Name	Description
C5233	NCB31HK-103X	C CAP.	0.01μF 50V K
C5234	NCB31HK-103X	C CAP.	0.01μF 50V K
C5235	NCB31HK-103X	C CAP.	0.01μF 50V K
C5236	QETNLCM-107	E CAP.	100μF 16V M
C5237	NCB31HK-103X	C CAP.	0.01μF 50V K
C5238	QETNLCM-107	E CAP.	100μF 16V M
C5239	NCB31HK-103X	C CAP.	0.01μF 50V K
C5240	NCB31HK-103X	C CAP.	0.01μF 50V K
C5241	NCB31HK-103X	C CAP.	0.01μF 50V K
C5242	QETNLCM-107	E CAP.	100μF 16V M
C5243	NCB31HK-103X	C CAP.	0.01μF 50V K
C5246	NDC31HJ-181X	C CAP.	180pF 50V J
C5247	NCB31HK-103X	C CAP.	0.01μF 50V K
C5251	QETNLEM-476	E CAP.	47μF 25V M
C5252	NCB31HK-103X	C CAP.	0.01μF 50V K
C5253	NDC31HJ-820X	C CAP.	82pF 50V J
C5255	NDC31HJ-470X	C CAP.	47pF 50V J
C5263	NDC31HJ-150X	C CAP.	15pF 50V J
C5391	QETNLHM-474	E CAP.	0.47μF 50V M
C5392	QETNLHM-474	E CAP.	0.47μF 50V M
C5501	QETNLHM-225	E CAP.	2.2μF 50V M
C5502	QETNLHM-225	E CAP.	2.2μF 50V M
C5503	QETNLHM-106	E CAP.	10μF 50V M
C5504	QENCLCM-106	E CAP.	10μF 16V M
C5506	QETNLHM-106	E CAP.	10μF 50V M
C5508	QETNLHM-106	E CAP.	10μF 50V M
C5509	NCB31HK-103X	C CAP.	0.01μF 50V K
C5520	QETNLHM-225	E CAP.	2.2μF 50V M
C5521	QETNLHM-225	E CAP.	2.2μF 50V M
C5531	NCB31HK-103X	C CAP.	0.01μF 50V K
C5532	QETNLEM-476	E CAP.	47μF 25V M
C5533	NCB31HK-103X	C CAP.	0.01μF 50V K
C5534	QENCLCM-106	E CAP.	10μF 16V M
L5201	QUY153-050Y	IM BUS WIRE	
L5202	QQL244K-150Z	COIL	15μH K
L5211	QQL244K-4R7Z	COIL	4.7μH K
L5241	QQL244K-4R7Z	COIL	4.7μH K
L5242	QUY153-050Y	IM BUS WIRE	
L5243	QQL244K-4R7Z	COIL	4.7μH K
L5244	QQL244K-4R7Z	COIL	4.7μH K
L5251	QUY153-050Y	IM BUS WIRE	
L5261	QQL244K-150Z	COIL	15μH K
J5501	QNZ0454-001	AV JACK	
J5502	QNN0349-001	PIN JACK	
J5503	QNN0348-001	PIN JACK	
CN5001	QGB1505K1-35	B TO B CONNE	
CN5006	QGA2501C5-05Z	W TO B CONNE	

FRONT CONTROL P.W. BOARD ASS'Y (SGJ-6002A-M2)

△ Symbol No.	Part No.	Part Name	Description
R6401	NRSA63J-750X	MG R	75Ω 1/16W J
R6402	NRSA63J-224X	MG R	220kΩ 1/16W J
R6403	NRSA63J-224X	MG R	220kΩ 1/16W J
R6702	NRSA63J-102X	MG R	1kΩ 1/16W J
R6703	NRSA63J-102X	MG R	1kΩ 1/16W J
R6704	NRSA63J-152X	MG R	1.5kΩ 1/16W J
R6705	NRSA63J-272X	MG R	2.7kΩ 1/16W J
R6706	NRSA63J-562X	MG R	5.6kΩ 1/16W J
C6401	QETNLHM-106	E CAP.	10μF 50V M
C6402	QETNLHM-225	E CAP.	2.2μF 50V M
C6403	QETNLHM-225	E CAP.	2.2μF 50V M
LC6401	QQR1199-001	N FILTER	
S6702	QSW0619-003Z	TACT SWITCH	MENU
S6703	QSW0619-003Z	TACT SWITCH	CH-
S6704	QSW0619-003Z	TACT SWITCH	CH+
S6705	QSW0619-003Z	TACT SWITCH	VOL-
S6706	QSW0619-003Z	TACT SWITCH	VOL+
J6401	QNN0281-003	PIN JACK	
OR	CEM065-001	PIN JACK	
J6402	QNN0281-002	PIN JACK	
OR	CEM065-002	PIN JACK	
J6403	CEM072-003	PIN JACK	
OR	QNN0282-001	PIN JACK	
CN6006	QJB003-054010	SIN ID C-B WIRE	
CN6007	QJB003-064426	SIN ID C-B WIRE	

LED & POWER SW P.W. BOARD ASS'Y (SGJ-7001A-M2)

△ Symbol No.	Part No.	Part Name	Description
IC7701	LC30190-001B-A	LED HOLDER	
Q7702	GP1M281QK	IR DETECT UNIT	
D7701	UN2112	DIGIT TRANSISTOR	
R7708	LH22440	LE DIODE	
R7709	NRSA63J-152X	MG R	1.5kΩ 1/16W J
R7710	NRSA63J-561X	MG R	56kΩ 1/16W J
R7711	NRSA63J-101X	MG R	10kΩ 1/16W J
C7701	NRSA63J-101X	MG R	10kΩ 1/16W J
S7701	QETNLEM-476	E CAP.	47μF 25V M
	QSW0847-001	TACT SWITCH	POWER SW

3D Y/C SEP MODULE P.W. BOARD ASS'Y (SGJ0Y001A-M2) [AV-32F803/Y ONLY]

△ Symbol No.	Part No.	Part Name	Description
	SGJ0Y001A-M2	3D Y/C SEP MODULE P	

REMOTE COTROL UNIT PARTS LIST

[AV-32F703/Y] (RM-C326G-1A)


△ Ref.No.	Part No.	Part Name	Description
1	URS2EC1286C	BATTERY COVER	

[AV-32F713/Y] (RM-C326-1A)


△ Ref.No.	Part No.	Part Name	Description
1	URS2EC1286A	BATTERY COVER	

[AV-32F803/Y] (RM-C325G-1A)

△ Ref.No.	Part No.	Part Name	Description
1	URS2EC1286C	BATTERY COVER	



PACKING



[AV-32F703/Y] [AV-32F713/Y] [AV-32F803/Y]

PACKING PARTS LIST

△ Ref.No.	Part No.	Part Name	Description
1	LC10181-026B-A	PACKING CASE	
2	CM36616-001-A	CORNER LABEL	2pcs in 1set
3	LC11049-002A-A	CUSHION ASSY	4pcs in 1set
4	CP30055-A02-A	TOP COVER	
5	CP30056-004-A	POLY BAG	
6	QPA02503505	POLY BAG	
7	RM-C326G-1A	REMOCON UNIT	[AV-32F703/Y]
7	RM-C326-1A	REMOCON UNIT	[AV-32F713/Y]
7	RM-C325G-1A	REMOCON UNIT	[AV-32F803/Y]
△ 8	LCT1134-001B-A	INSTRUCTIONS BOOK	
9	BT-51028-2Q	REGISTRATION C	
10	BT-52006-1Q	WARRANTY CARD	

JVC SERVICE & ENGINEERING COMPANY OF AMERICA

DIVISION OF JVC AMERICAS CORP.

Head office :	1700 Valley Road, Wayne, New Jersey 07470	(973)315-5000
East Coast :	10 New Maple Avenue, Pine Brook, New Jersey 07058	(973)396-1000
Midwest :	705 Enterprise St. Aurora, Illinois 60504	(630)851-7855
West Coast :	5665 Corporate Avenue, Cypress, California 90630	(714)229-8011
Southwest :	10700 Hammerly, Suite 105, Houston, Texas 77043	(713)935-9331
Hawaii :	2969 Mapunapuna Place, Honolulu, Hawaii 96819	(808)833-5828
Southeast :	1500 Lakes Parkway, Lawrenceville, Georgia 30243	(770)339-2582

JVC CANADA INC.

Head office :	21 Finchdene Square Scarborough, Ontario M1X 1A7	(416)293-1311
Vancouver :	13040 Worster Court Richmond B.C. V6V 2B3	(604)270-1311

JVC[®]