



## Specifications

### Video:

> 70 dBmV @ 100 MHz

### IF/RF:

> 52 dBmV @ 950 MHz

### Stereo Audio:

Balanced, detachable screw terminals

### Clock Accuracy:

+ 1 sec per day @ 20° C

### Power Requirement for External Power Supply:

117 VAC + 10 %, 50/60 Hz  
(240 VAC available)

### Physical:

2.0" H X 4.25" W X 6.5" D

Weight: 1 lb.

# Program Timer jr.

model  
**631A**

## Features

- Small size
- 'F' connectors
- Unused Video terminated to 75  $\Omega$
- Balanced stereo audio
- Six ON/OFF commands per day
- Block programming for Monday through Friday
- Battery backup of clock on power loss (1 AA)
- Includes power pack
- May be used for IF/RF from 0 to > 950 MHz.



## Description

Monroe Electronics' 631A Program Timer Jr. provides a 2x1 (AB) balanced stereo audio follow video switch, with separate timed commands.

The 631A has been designed to be as simple as possible to program. Setting the time of day, programming of individual days, or an entire weekly schedule is accomplished with only five keystrokes. Manual override of output is accomplished with a single key stroke.

Four selectable block program variations allow for quick and simple programming:

**Monday through Friday**  
**Monday through Saturday**  
**Monday through Sunday**  
**Saturday/Sunday**