

**Nokia Customer Care
6265/6265i/6268 (RM-66)
Mobile Terminals**

Parts Lists – Models 6265/6268

Contents	Page
6265/6268 Parts List – Version 003—Engine Code 0202801	3

6265/6268 Parts List – Version 003—Engine Code 0202801

Item	Side	X	Y	Description
A0001	Bottom	P	6	BB SHIELD ASSEMBLY
A0002	Bottom	J	5	RX SHIELD ASSEMBLY
A0003	Bottom	J	8	TX SHIELD ASSEMBLY
A0004	Bottom	D	8	DUPLEXOR SHIELD ASSEMBLY
A0005	Bottom	B	4	GPS SHIELD ASSEMBLY
A0006	Bottom	F	8	DC DC SHIELD COVER
B2200	Bottom	P	3	CRYSTAL 32.768KHZ +/-30PPM 12.5PF
C2001	Bottom	H	7	CHIPCAP X7R 10N K 50V 0603
C2002	Bottom	G	9	CHIPCAP NP0 47P J 50V 0402
C2004	Bottom	P	2	CHIPCAP X7R 1N0 K 50V 0402
C2005	Bottom	Q	2	CHIPCAP NP0 22P J 50V 0402
C2006	Top	T	3	CHIPCAP X5R 100N M 16V 0402
C2007	Top	S	4	CHIPCAP X5R 1U K 6V3 0402
C2008	Top	K	3	CHIPCAP X5R 1U K 6V3 0402
C2009	Top	L	3	CHIPCAP X7R 10N K 16V 0402
C2016	Bottom	S	8	CHIPCAP NP0 33P J 50V 0402
C2017	Bottom	S	8	CHIPCAP NP0 33P J 50V 0402
C2018	Bottom	S	8	CHIPCAP NP0 33P J 50V 0402
C2019	Bottom	S	8	CHIPCAP NP0 33P J 50V 0402
C2020	Top	S	6	CHIPCAP X7R 3N3 J 50V 0402
C2021	Top	T	6	CHIPCAP X7R 3N3 J 50V 0402
C2022	Top	S	7	CHIPCAP X7R 3N3 J 50V 0402
C2023	Top	T	7	CHIPCAP X7R 3N3 J 50V 0402
C2024	Top	S	8	CHIPCAP X7R 3N3 J 50V 0402
C2025	Top	T	8	CHIPCAP X7R 3N3 J 50V 0402
C2100	Top	S	5	CHIPCAP X5R 100N M 16V 0402
C2101	Top	T	5	CHIPCAP X5R 100N M 16V 0402
C2102	Bottom	H	3	CHIPCAP X5R 100N M 16V 0402
C2103	Bottom	G	3	CHIPCAP X5R 100N M 16V 0402
C2104	Top	S	5	CHIPCAP X5R 100N M 16V 0402
C2105	Bottom	G	3	CHIPCAP X5R 100N M 16V 0402

Item	Side	X	Y	Description
C2106	Bottom	G	4	CHIPCAP X5R 10U M 6V3 0805
C2107	Bottom	F	2	CHIPCAP NP0 47P J 50V 0402
C2108	Bottom	F	4	CHIPCAP X5R 10U M 6V3 0805
C2109	Bottom	G	4	CHIPCAP X5R 10U M 6V3 0805
C2110	Bottom	F	2	CHIPCAP NP0 47P J 50V 0402
C2111	Bottom	F	2	CHIPCAP X7R 3N3 J 50V 0402
C2112	Bottom	F	3	CHIPCAP NP0 47P J 50V 0402
C2113	Bottom	F	3	CHIPCAP X7R 3N3 J 50V 0402
C2114	Bottom	F	3	CHIPCAP X5R 100N M 16V 0402
C2115	Bottom	S	8	CHIPCAP X7R 390P J 50V 0402
C2116	Bottom	P	3	CHIPCAP X5R 100N M 16V 0402
C2117	Bottom	H	3	CHIPCAP X7R 10N K 16V 0402
C2118	Bottom	S	2	CHIPCAP X5R 100N M 16V 0402
C2119	Bottom	S	2	CHIPCAP X5R 100N M 16V 0402
C2120	Bottom	S	2	CHIPCAP X5R 100N M 16V 0402
C2121	Bottom	B	2	CHIPCAP X7R 680P J 50V 0402
C2122	Bottom	C	2	CHIPCAP X7R 47N K 10V 0402
C2123	Bottom	B	2	CHIPCAP X5R 1U5 K 4V 0402
C2124	Bottom	B	1	CHIPCAP X5R 1U K 6V3 0603
C2125	Bottom	G	3	CHIPCAP NP0 47P J 50V 0402
C2126	Bottom	C	2	CHIPCAP X7R 47N K 10V 0402
C2127	Bottom	B	2	CHIPCAP X7R 680P J 50V 0402
C2130	Bottom	F	2	CHIPCAP X7R 3N3 J 50V 0402
C2200	Bottom	M	3	CHIPCAP X5R 1U K 6V3 0603
C2201	Bottom	N	3	CHIPCAP X7R 10N K 16V 0402
C2202	Bottom	P	4	CHIPCAP X7R 10N K 16V 0402
C2203	Bottom	P	4	CHIPCAP X5R 1U5 K 4V 0402
C2204	Bottom	M	3	CHIPCAP X5R 100N M 16V 0402
C2205	Bottom	N	3	CHIPCAP X5R 1U5 K 4V 0402
C2206	Bottom	N	3	CHIPCAP X5R 1U5 K 4V 0402
C2207	Bottom	O	3	CHIPCAP X5R 1U5 K 4V 0402
C2208	Bottom	P	4	CHIPCAP X5R 1U5 K 4V 0402

Item	Side	X	Y	Description
C2209	Bottom	P	4	CHIPCAP X5R 1U5 K 4V 0402
C2210	Bottom	P	3	CHIPCAP NP0 10P J 50V 0402
C2211	Bottom	P	3	CHIPCAP NP0 10P J 50V 0402
C2212	Bottom	P	4	CHIPCAP X5R 1U5 K 4V 0402
C2213	Bottom	O	3	CHIPCAP X5R 1U5 K 4V 0402
C2214	Bottom	O	3	CHIPCAP X5R 1U5 K 4V 0402
C2215	Bottom	P	3	CHIPCAP X5R 1U5 K 4V 0402
C2216	Bottom	P	3	CHIPCAP X5R 1U5 K 4V 0402
C2217	Bottom	N	5	CHIPCAP X5R 100N M 16V 0402
C2218	Bottom	M	5	CHIPCAP X5R 100N M 16V 0402
C2220	Bottom	P	5	CHIPCAP X5R 1U5 K 4V 0402
C2221	Bottom	M	5	CHIPCAP X5R 100N M 16V 0402
C2222	Bottom	M	5	CHIPCAP X5R 100N M 16V 0402
C2223	Bottom	M	3	CHIPCAP X5R 1U K 6V3 0603
C2224	Bottom	N	3	CHIPCAP X5R 220N K 6.3V 0402
C2225	Bottom	M	5	CHIPCAP X5R 1U5 K 4V 0402
C2226	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2227	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2228	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2230	Bottom	O	8	CHIPCAP X7R 10N K 16V 0402
C2231	Bottom	O	3	CHIPCAP X7R 10N K 16V 0402
C2232	Bottom	L	3	CHIPCAP X5R 10U M 6V3 0805
C2233	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2234	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2235	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2236	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2237	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2238	Bottom	M	3	CHIPCAP X5R 1U5 K 4V 0402
C2239	Bottom	M	3	CHIPCAP X5R 1U K 6V3 0603
C2240	Bottom	M	3	CHIPCAP X5R 1U K 6V3 0603
C2241	Bottom	M	4	CHIPCAP X5R 1U5 K 4V 0402
C2300	Bottom	Q	9	CHIPCAP X5R 10UF 6V3 0603

Item	Side	X	Y	Description
C2302	Bottom	R	9	CHIPCAP X5R 4U7 K 6.3V 0603
C2303	Bottom	R	9	CHIPCAP X5R 4U7 K 6.3V 0603
C2304	Bottom	O	9	CHIPCAP X5R 100N M 16V 0402
C2400	Top	L	3	CHIPCAP NP0 10P J 50V 0402
C2401	Top	L	3	CHIPCAP X5R 100N M 16V 0402
C2404	Bottom	R	8	CHIPCAP X5R 100N M 16V 0402
C2405	Bottom	R	8	CHIPCAP X5R 4U7 K 6.3V 0603
C2406	Bottom	S	8	CHIPCAP X5R 100N M 16V 0402
C2407	Bottom	R	5	CHIPCAP X5R 1U0 K 25V T 1.0 1206
C2408	Bottom	R	5	CHIPCAP X5R 1U0 K 25V T 1.0 1206
C2409	Bottom	O	8	CHIPCAP X5R 1U K 16V 0603
C2410	Bottom	O	8	CHIPCAP X5R 1U K 16V 0603
C2411	Bottom	O	8	CHIPCAP X5R 1U K 16V 0603
C2414	Bottom	O	9	CHIPCAP X5R 1U K 16V 0603
C2415	Bottom	E	5	CHIPCAP X5R 100N M 16V 0402
C2600	Bottom	O	2	CHIPCAP X5R 100N M 16V 0402
C2602	Bottom	M	2	CHIPCAP X5R 4U7 K 6.3V 0603
C2700	Bottom	R	7	CHIPCAP X5R 100N M 16V 0402
C2800	Bottom	N	8	CHIPCAP X5R 1U5 K 4V 0402
C2801	Bottom	P	7	CHIPCAP X7R 10N K 16V 0402
C2802	Bottom	M	6	CHIPCAP X7R 10N K 16V 0402
C2803	Bottom	P	6	CHIPCAP X7R 10N K 16V 0402
C2804	Bottom	N	5	CHIPCAP X7R 10N K 16V 0402
C2805	Bottom	M	7	CHIPCAP X7R 10N K 16V 0402
C2806	Bottom	O	5	CHIPCAP X7R 10N K 16V 0402
C2807	Bottom	M	5	CHIPCAP X7R 10N K 16V 0402
C2808	Bottom	P	7	CHIPCAP X7R 10N K 16V 0402
C2809	Bottom	P	8	CHIPCAP X7R 10N K 16V 0402
C2810	Bottom	N	8	CHIPCAP X7R 10N K 16V 0402
C2900	Bottom	L	3	CHIPCAP X7R 10N K 16V 0402
C2901	Bottom	L	4	CHIPCAP X7R 10N K 16V 0402
C2902	Bottom	N	8	CHIPCAP X7R 10N K 16V 0402

Item	Side	X	Y	Description
C2903	Bottom	L	8	CHIPCAP X7R 1N0 K 50V 0402
C2904	Bottom	N	8	CHIPCAP X7R 33N K 10V 0402
C2905	Bottom	M	5	CHIPCAP X7R 10N K 16V 0402
C2906	Bottom	M	8	CHIPCAP X7R 1N0 K 50V 0402
C2907	Bottom	M	7	CHIPCAP X7R 33N K 10V 0402
C2908	Bottom	M	5	CHIPCAP X7R 47N K 10V 0402
C2909	Bottom	H	7	CHIPCAP X7R 4N7 J 25V 0402
C2910	Bottom	M	6	CHIPCAP X7R 47N K 10V 0402
C3000	Bottom	R	4	CHIPCAP X7R 10N K 16V 0402
C3001	Bottom	R	6	CHIPCAP X5R 100N M 16V 0402
C3002	Bottom	P	5	CHIPCAP X7R 10N K 16V 0402
C3003	Bottom	P	5	CHIPCAP X5R 100N M 16V 0402
C3004	Bottom	P	8	CHIPCAP X5R 100N M 16V 0402
C6000	Bottom	R	3	CHIPCAP NP0 15P J 50V 0402
C6001	Bottom	Q	3	CHIPCAP X5R 4U7 K 6.3V 0603
C6003	Bottom	Q	3	CHIPCAP X5R 4U7 K 6.3V 0603
C6004	Bottom	Q	4	CHIPCAP X5R 1U K 6V3 0402
C6005	Bottom	Q	3	CHIPCAP X5R 1U K 6V3 0402
C6006	Bottom	R	4	CHIPCAP X5R 100N M 16V 0402
C6007	Bottom	R	3	CHIPCAP X5R 100N M 16V 0402
C6008	Bottom	R	4	CHIPCAP X5R 470N K 6.3V 0402
C6009	Bottom	Q	3	CHIPCAP X5R 1U K 6V3 0402
C6010	Bottom	Q	3	CHIPCAP X5R 470N K 6.3V 0402
C6012	Bottom	Q	3	CHIPCAP X5R 4U7 K 6.3V 0603
C6100	Bottom	N	8	CHIPCAP X5R 100N M 16V 0402
C6101	Bottom	N	8	CHIPCAP X5R 100N M 16V 0402
C6102	Bottom	N	9	CHIPCAP NP0 100P J 50V 0402
C6103	Bottom	M	9	CHIPCAP NP0 47P J 50V 0402
C6104	Bottom	N	9	CHIPCAP NP0 27P J 50V 0402
C6105	Bottom	M	9	CHIPCAP X7R 10N K 16V 0402
C6106	Bottom	M	9	CHIPCAP X7R 10N K 16V 0402
C6107	Bottom	M	9	CHIPCAP X5R 100N M 16V 0402

Item	Side	X	Y	Description
C6108	Bottom	M	8	CHIPCAP X7R 10N K 16V 0402
C6109	Bottom	M	8	CHIPCAP X7R 33N K 10V 0402
C6110	Bottom	P	3	CHIPCAP X5R 100N M 16V 0402
C6111	Bottom	P	4	CHIPCAP X5R 100N M 16V 0402
C6112	Bottom	N	9	CHIPCAP X7R 33N K 10V 0402
C6113	Bottom	M	9	CHIPCAP X7R 33N K 10V 0402
C6114	Bottom	N	8	CHIPCAP X7R 33N K 10V 0402
C6115	Bottom	N	9	CHIPCAP X5R 100N M 16V 0402
C6252	Bottom	D	2	CHIPCAP NP0 2P2 C 50V 0402
C6600	Bottom	E	5	CHIPCAP X5R 220N K 6.3V 0402
C6601	Bottom	E	5	CHIPCAP X5R 100N M 16V 0402
C6602	Bottom	E	5	CHIPCAP NP0 39P J 50V 0402
C6603	Bottom	H	6	CHIPCAP X5R 100N M 16V 0402
C6604	Bottom	H	6	CHIPCAP NP0 39P J 50V 0402
C6605	Bottom	D	5	CHIPCAP NP0 10P J 50V 0402
C6607	Bottom	E	6	CHIPCAP X7R 10N K 16V 0402
C6608	Bottom	E	6	CHIPCAP X5R 100N M 16V 0402
C6612	Bottom	C	6	CHIPCAP X5R 4U7 K 6.3V 0603
C6613	Bottom	C	5	CHIPCAP X5R 10U M 6V3 0805
C6614	Bottom	C	6	CHIPCAP X5R 4U7 K 6.3V 0603
C6615	Bottom	E	5	CHIPCAP X5R 100N M 16V 0402
C6617	Bottom	C	6	CHIPCAP X5R 4U7 K 6.3V 0603
C6618	Bottom	B	5	CHIPCAP X7R 33N K 10V 0402
C6619	Bottom	C	6	CHIPCAP X5R 4U7 K 6.3V 0603
C6621	Bottom	B	6	CHIPCAP NP0 10P J 50V 0402
C7000	Bottom	J	9	CHIPCAP X7R 10N J 16V 0402
C7001	Bottom	J	9	CHIPCAP X7R 10N J 16V 0402
C7002	Bottom	L	8	CHIPCAP X5R 100N K 10V 0402
C7003	Bottom	K	9	CHIPCAP NP0 3P3 C 50V 0402
C7004	Bottom	K	9	CHIPCAP NP0 220P J 25V 0402
C7005	Bottom	L	9	CHIPCAP NP0 100P J 50V 0402
C7006	Bottom	L	9	CHIPCAP NP0 2N2 J 16V 0603

Item	Side	X	Y	Description
C7007	Bottom	L	9	CHIPCAP NP0 100P J 50V 0402
C7008	Bottom	L	9	CHIPCAP NP0 4P7 C 50V 0402
C7009	Bottom	L	9	CHIPCAP X5R 1U K 6V3 0402
C7011	Bottom	K	9	CHIPCAP X7R 10N J 16V 0402
C7012	Bottom	K	9	CHIPCAP NP0 18P J 50V 0402
C7013	Bottom	L	8	CHIPCAP NP0 33P J 50V 0402
C7014	Bottom	K	8	CHIPCAP NP0 18P J 50V 0402
C7015	Bottom	K	8	CHIPCAP NP0 33P J 50V 0402
C7016	Bottom	K	8	CHIPCAP X7R 10N J 16V 0402
C7017	Bottom	K	8	CHIPCAP NP0 47P J 50V 0402
C7018	Bottom	K	9	CHIPCAP NP0 10P J 50V 0402
C7019	Bottom	L	8	CHIPCAP NP0 12P J 50V 0402
C7020	Bottom	L	9	CHIPCAP NP0 18P J 50V 0402
C7021	Bottom	L	8	CHIPCAP X7R 10N J 16V 0402
C7022	Bottom	J	7	CHIPCAP NP0 3P3 C 50V 0402
C7023	Bottom	J	8	CHIPCAP NP0 1P2 C 50V 0402
C7024	Bottom	J	8	CHIPCAP NP0 1P2 C 50V 0402
C7026	Bottom	J	9	CHIPCAP NP0 0P5 C 50V 0402
C7027	Bottom	J	8	CHIPCAP NP0 0P5 C 50V 0402
C7029	Bottom	K	9	CHIPCAP NP0 3P3 C 50V 0402
C7030	Bottom	K	9	CHIPCAP NP0 3P3 C 50V 0402
C7031	Bottom	L	8	CHIPCAP NP0 8P2 C 50V 0402
C7100	Bottom	L	5	CHIPCAP X7R 10N J 16V 0402
C7101	Bottom	L	5	CHIPCAP X5R 330N K 10V 0603
C7102	Bottom	L	5	CHIPCAP X7R 33N K 10V 0402
C7103	Bottom	K	5	CHIPCAP NP0 33P J 50V 0402
C7104	Bottom	K	5	CHIPCAP X7R 1N0 J 50V 0402
C7105	Bottom	L	4	CHIPCAP X7R 10N K 16V 0402
C7106	Bottom	L	5	CHIPCAP X7R 10N K 16V 0402
C7107	Bottom	L	4	CHIPCAP X7R 10N K 16V 0402
C7108	Bottom	K	5	CHIPCAP X7R 10N K 16V 0402
C7109	Bottom	K	4	CHIPCAP X7R 10N K 16V 0402

Item	Side	X	Y	Description
C7110	Bottom	L	4	CHIPCAP X7R 10N K 16V 0402
C7111	Bottom	L	4	CHIPCAP X7R 10N K 16V 0402
C7112	Bottom	K	5	CHIPCAP X7R 10N K 16V 0402
C7113	Bottom	K	4	CHIPCAP X7R 10N K 16V 0402
C7162	Bottom	H	3	CHIPCAP NP0 100P J 50V 0402
C7163	Bottom	I	3	CHIPCAP NP0 100P J 50V 0402
C7164	Bottom	I	3	CHIPCAP NP0 100P J 50V 0402
C7165	Bottom	H	5	CHIPCAP NP0 56P J 50V 0402
C7166	Bottom	H	5	CHIPCAP NP0 1P8 C 50V 0402
C7167	Bottom	H	4	CHIPCAP NP0 12P J 50V 0402
C7168	Bottom	H	4	CHIPCAP X5R 100N K 10V 0402
C7169	Bottom	H	4	CHIPCAP NP0 1P2 C 50V 0402
C7170	Bottom	I	5	CHIPCAP NP0 100P J 50V 0402
C7171	Bottom	I	5	CHIPCAP NP0 5P6 C 50V 0402
C7172	Bottom	H	5	CHIPCAP X7R 47N K 10V 0402
C7173	Bottom	H	4	CHIPCAP NP0 12P J 50V 0402
C7174	Bottom	I	4	CHIPCAP X7R 3N3 J 50V 0402
C7175	Bottom	I	4	CHIPCAP NP0 22P J 50V 0402
C7176	Bottom	I	5	CHIPCAP X7R 1N0 J 50V 0402
C7177	Bottom	I	5	CHIPCAP NP0 4P7 C 50V 0402
C7178	Bottom	I	5	CHIPCAP NP0 3P9 C 50V 0402
C7179	Bottom	J	5	CHIPCAP NP0 10P J 50V 0402
C7180	Bottom	J	5	CHIPCAP NP0 6P8 C 50V 0402
C7181	Bottom	J	5	CHIPCAP NP0 6P8 C 50V 0402
C7182	Bottom	J	4	CHIPCAP X7R 3N3 J 50V 0402
C7183	Bottom	I	4	CHIPCAP X5R 100N K 10V 0402
C7184	Bottom	J	4	CHIPCAP NP0 2P2 C 50V 0402
C7185	Bottom	I	4	CHIPCAP NP0 100P J 50V 0402
C7187	Bottom	K	3	CHIPCAP NP0 8P2 C 50V 0402
C7188	Bottom	K	4	CHIPCAP NP0 8P2 C 50V 0402
C7200	Bottom	K	6	CHIPCAP X5R 1U K 6V3 0402
C7201	Bottom	K	6	CHIPCAP X7R 10N J 16V 0402

Item	Side	X	Y	Description
C7202	Bottom	K	6	CHIPCAP X7R 1N0 J 50V 0402
C7203	Bottom	L	7	CHIPCAP NP0 470P J 6V3 0402
C7204	Bottom	L	7	CHIPCAP NP0 100P J 50V 0402
C7206	Bottom	K	9	CHIPCAP NP0 470P J 6V3 0402
C7207	Bottom	L	4	CHIPCAP NP0 470P J 6V3 0402
C7208	Bottom	K	7	CHIPCAP X7R 470P J 50V 0402
C7209	Bottom	L	6	CHIPCAP X7R 10N J 16V 0402
C7210	Bottom	L	6	CHIPCAP X5R 100N K 10V 0402
C7211	Bottom	K	7	CHIPCAP NP0 47P J 50V 0402
C7212	Bottom	I	6	CHIPCAP NP0 1P8 C 50V 0402
C7213	Bottom	K	6	CHIPCAP X7R 3N3 J 50V 0402
C7214	Bottom	K	6	CHIPCAP X7R 33N K 10V 0402
C7215	Bottom	K	6	CHIPCAP X7R 6N8 K 25V 0402
C7216	Bottom	J	6	CHIPCAP X7R 1N0 J 50V 0402
C7217	Bottom	J	7	CHIPCAP X7R 1N0 J 50V 0402
C7218	Bottom	J	6	CHIPCAP X5R 1U K 6V3 0402
C7219	Bottom	J	6	CHIPCAP X7R 10N J 16V 0402
C7220	Bottom	I	7	CHIPCAP X5R 100N K 10V 0402
C7221	Bottom	L	6	CHIPCAP X7R 10N J 16V 0402
C7222	Bottom	L	6	CHIPCAP X5R 100N K 10V 0402
C7300	Bottom	I	8	CHIPCAP X7R 1N0 J 50V 0402
C7302	Bottom	I	9	CHIPCAP X7R 10N J 16V 0402
C7303	Bottom	I	8	CHIPCAP NP0 3P3 C 50V 0402
C7304	Bottom	H	9	CHIPCAP NP0 15P J 50V 0402
C7305	Bottom	I	9	CHIPCAP X7R 1N0 J 50V 0402
C7306	Bottom	I	9	CHIPCAP NP0 10P J 50V 0402
C7311	Bottom	C	9	CHIPCAP NP0 10P J 50V 0402
C7312	Bottom	C	9	CHIPCAP NP0 47P J 50V 0402
C7313	Bottom	C	7	CHIPCAP X7R 10N J 16V 0402
C7314	Bottom	C	7	CHIPCAP NP0 10P J 50V 0402
C7315	Bottom	D	7	CHIPCAP X7R 3N3 J 50V 0402
C7316	Bottom	C	7	CHIPCAP X7R 3N3 J 50V 0402

Item	Side	X	Y	Description
C7317	Bottom	H	8	CHIPCAP X5R 10U M 6V3 0805
C7318	Bottom	H	9	CHIPCAP X5R 10U M 6V3 0805
C7319	Bottom	I	8	CHIPCAP NP0 270P J 50V 0402
C7320	Bottom	I	7	CHIPCAP NP0 100P J 50V 0402
C7321	Bottom	I	8	CHIPCAP X7R 1N0 J 50V 0402
C7322	Bottom	H	8	CHIPCAP X7R 1N0 J 50V 0402
C7323	Bottom	I	8	CHIPCAP NP0 3P3 C 50V 0402
C7324	Bottom	I	8	CHIPCAP NP0 3P3 C 50V 0402
C7325	Bottom	H	8	CHIPCAP NP0 5P6 C 50V 0402
C7326	Bottom	H	9	CHIPCAP NP0 2P7 C 50V 0402
C7350	Bottom	E	7	CHIPCAP NP0 47P J 50V 0402
C7351	Bottom	F	7	CHIPCAP NP0 47P J 50V 0402
C7352	Bottom	E	7	CHIPCAP NP0 10P J 50V 0402
C7353	Bottom	F	8	CHIPCAP NP0 47P J 50V 0402
C7354	Bottom	F	7	CHIPCAP X5R 4U7 K 6.3V 0603
C7355	Bottom	F	8	CHIPCAP X5R 4U7 K 6.3V 0603
C7356	Bottom	F	9	CHIPCAP X7R 10N K 16V 0402
C7357	Bottom	F	7	CHIPCAP X5R 10U M 6V3 0805
C7358	Bottom	F	8	CHIPCAP X5R 10U M 6V3 0805
D2200	Bottom	O	4	UEMEK2v0 LF WDNA TFBGA244
D2400	Bottom	D	4	Dual 2 input OR gate, VSSOP package
D2800	Bottom	N	7	TIKUEDGE v2.0 LF C027 GZG289
D3000	Bottom	Q	5	COMBO 128MNOR+256MNAND+128MSDRAM FBGA133
D6601	Bottom	D	6	HW ACCELERATOR STV0984N
E7300	Bottom	B	7	GROUND SPACER PAD
F2000	Bottom	S	2	SM FUSE F 2.0A 32V 0603
G7200	Bottom	K	7	VCTCXO 19.2MHZ +-2PPM 2.78V 2.2MA
G7201	Bottom	J	6	UHF VCO 986-1034MHz/2040-2140MHz
L2000	Bottom	Q	2	FERR.BEAD 220R/100M 2A 0R05 0603
L2001	Top	S	4	FERRITE BEAD 0.6R 600R/100MZ 0402
L2002	Top	S	3	FERRITE BEAD 0.6R 600R/100MZ 0402
L2003	Top	S	4	FERRITE BEAD 0.6R 600R/100MZ 0402

Item	Side	X	Y	Description
L2004	Top	S	6	CHIP BEAD ARRAY 2X1000R 0R75 0405
L2005	Top	S	7	CHIP BEAD ARRAY 2X1000R 0R75 0405
L2006	Top	S	8	CHIP BEAD ARRAY 2X1000R 0R75 0405
L2100	Bottom	D	2	FERRITE BEAD 0.6R 600R/100MZ 0402
L2101	Bottom	D	3	FERRITE BEAD 0.6R 600R/100MZ 0402
L2102	Bottom	F	3	FERRITE BEAD 0.6R 600R/100MZ 0402
L2103	Bottom	G	3	CHIP BEAD ARRAY 2X1000R 0R75 0405
L2104	Bottom	B	7	CHIP BEAD ARRAY 2X220R 0405
L2105	Bottom	G	2	CHIP COIL 100N J Q16/300MHZ 0402
L2301	Bottom	Q	9	CHOKE 10UH M 0.49A 3.0X2.8X1.2MM
L2302	Bottom	P	8	FERRITE BEAD 0R35 68R/100MHZ 0603
L2400	Bottom	R	8	FERR.BEAD 0R03 42R/100MHZ 3A 0805
L2401	Bottom	R	7	CHOKE 3.3UH 0R252 0A82 310 case size
L6000	Bottom	R	3	CHIP COIL 22N J Q28/800MHZ 0402
L6001	Bottom	R	3	CHIP COIL 2N2 +-0N3 Q30/800M 0402
L6100	Bottom	N	9	CHIP COIL 68N J Q17/300MHZ 0402
L6101	Bottom	N	9	CHIP COIL 120NH J Q8/100MHZ 0402
L6102	Bottom	M	9	CHIP COIL 47N J Q23/800MHZ 0402
L6253	Bottom	D	2	CHIP COIL 15N G Q25/1GHZ 0402
L7000	Bottom	L	9	CHIP COIL 27N J Q27/800MHZ 0402
L7001	Bottom	K	8	CHIP COIL 27N J Q27/800MHZ 0402
L7002	Bottom	K	8	CHIP COIL 33N J Q23/800MHZ 0402
L7003	Bottom	J	8	CHIP COIL 27N J Q27/800MHZ 0402
L7004	Bottom	K	8	CHIP COIL 6N8 J Q27/800MHZ 0402
L7005	Bottom	K	8	CHIP COIL 12N J Q31/800MHZ 0402
L7006	Bottom	J	8	CHIP COIL 6N8 J Q27/800MHZ 0402
L7101	Bottom	K	5	CHIP COIL 33NH J Q12/100MHZ 0603
L7160	Bottom	H	4	CHIP COIL 6N2 J Q20/250MHZ 0402
L7161	Bottom	H	5	CHIP COIL 19N J Q25/250MHZ 0402
L7162	Bottom	I	4	CHIP COIL 12N J Q31/800MHZ 0402
L7163	Bottom	I	4	CHIP COIL 3N3 +-0N3 Q28/800M 0402
L7164	Bottom	I	5	CHIP COIL 82N +-0N3 Q17/300M 0402

Item	Side	X	Y	Description
L7165	Bottom	H	5	CHIP COIL 12N J Q31/800MHZ 0402
L7166	Bottom	H	4	CHIP COIL 3N3 +-0N3 Q28/800M 0402
L7167	Bottom	I	5	CHIP COIL 220N J Q8/50MHZ 0603
L7168	Bottom	I	4	CHIP COIL 18N J Q29/800MHZ 0402
L7169	Bottom	H	5	CHIP COIL 15N J Q30/800MHZ 0402
L7170	Bottom	I	4	CHIP COIL 82N +-0N3 Q17/300M 0402
L7171	Bottom	I	5	CHIP COIL 180N J Q13/100MHZ 0603
L7172	Bottom	J	5	CHIP COIL 120N J Q16/100MHZ 0603
L7173	Bottom	K	5	CHIP COIL 120N J Q16/100MHZ 0603
L7174	Bottom	J	5	CHIP COIL 220N J Q8/50MHZ 0603
L7175	Bottom	K	5	CHIP COIL 220N J Q8/50MHZ 0603
L7176	Bottom	J	5	CHIP COIL 120N J Q16/100MHZ 0603
L7177	Bottom	K	3	CHIP COIL 100N J Q12/100MHZ 0603
L7178	Bottom	L	3	CHIP COIL 120N J Q16/100MHZ 0603
L7179	Bottom	K	3	CHIP COIL 120N J Q16/100MHZ 0603
L7180	Bottom	H	4	CHIP COIL 8N2 J Q25/100MHz 0402
L7201	Bottom	I	6	CHIP COIL 3N3 +-0N3 Q28/800M 0402
L7301	Bottom	H	8	CHIP COIL 4N7 +-0N3 Q28/800M 0402
L7302	Bottom	C	8	DIR.COUPLER 1850-1910MHZ 1.6X0.8
L7303	Bottom	B	9	CHIP COIL 15N J Q24/250MHZ 0402
L7304	Bottom	C	7	CHIP COIL 10N J Q30/800MHZ 0402
L7305	Bottom	C	7	DIR.COUPLER 824-849MHZ 1.6X0.8MM
L7306	Bottom	H	8	CHIP COIL 15N J Q30/800MHZ 0402
L7350	Bottom	F	8	FERR.BEAD 0R03 42R/100MHZ 3A 0805
L7351	Bottom	E	8	INDUCT WW 1.5UH 0.096 OHM 1.1A
M2400	Bottom	I	2	SMD VIBRA MOTOR 1.3V 90MA 9000RPM
N2001	Top	K	3	NUT/CP2137 ASIC HBCC16++
N2100	Bottom	B	2	AF AMP 1W LM4990 NOPB 2.8V uSMD9
N2300	Bottom	R	9	DC/DC CONV LM3661-1.35V/1.05V
N2400	Top	L	3	HALL IC SWITCH SH248CSP VCC
N2401	Bottom	R	8	STEP-UP DC/DC CONV TK11891F-G SON3024-8
N2402	Bottom	O	9	WHITE LED DRIVER LM2796TLX USMD18

Item	Side	X	Y	Description
N2600	Bottom	P	2	IRDA RPM921 1.15Mbps 2V4
N6000	Bottom	Q	3	BRF6150 BTH ASIC ROM2.22 4.5x4.5 UBGA63
N6100	Bottom	N	9	FM RECEIVER TEA5761UK N3D (Ti) CSP
N6600	Bottom	B	5	REG LP3981YDX-2.8/NOPB 0.3A LLP-6
N6601	Bottom	B	6	LI VREG 1.2V/150mA (LP3990YD 1.2) LLP6
N6602	Bottom	C	6	LI VREG TK63118B-G 1.8V WLCSP4
N7000	Bottom	K	8	JUPITER D4 PMB3365G VQFN-40
N7100	Bottom	L	4	BATMAN RF RX ASIC STB7102FTR
N7160	Bottom	H	4	LNA/MIXER/DOWNCNTR ALFRED VQFN-24
N7200	Bottom	L	6	1XPLL/SYNTH 2.5GHZ(LMX2310U)MLF20
N7300	Bottom	I	9	PW AMP RF3448 CDMA1900
N7301	Bottom	I	8	PW AMP RF3449 CDMA800 LFM
N7302	Bottom	C	7	ASIP STPAC01F2 CDMA PWR DET BGA-8
N7350	Bottom	E	7	RF4013 V-E2.2 DC-DC BUCK CONV QFN 16
R2002	Bottom	P	9	NTC RES 0W1 47K J B 4050+-3% 0402
R2003	Top	S	3	CHIPRES 0W06 100K J 0402
R2004	Top	S	4	CHIPRES 0W06 33R J 0402
R2005	Top	T	4	CHIP VARISTOR VWM14V VC50V 0402
R2006	Top	S	5	ASIP USB2 FILTER BGA10 PBFREE
R2007	Top	K	4	CHIPRES 0W06 220K J 0402
R2008	Top	K	3	CHIPRES 0W06 220K J 0402
R2009	Top	S	7	CHIP VARISTOR VWM14V VC50V 0402
R2010	Top	T	7	CHIP VARISTOR VWM14V VC50V 0402
R2011	Top	S	7	CHIP VARISTOR VWM14V VC50V 0402
R2012	Top	T	7	CHIP VARISTOR VWM14V VC50V 0402
R2013	Bottom	P	8	ASIP 4XESD *** PB-FREE *** BGA5
R2100	Bottom	G	4	CHIPRES 0W06 10K J 0402
R2101	Bottom	G	3	CHIPRES 0W06 1KO J 0402
R2102	Bottom	F	2	CHIPRES 0W06 10R J 0402
R2103	Bottom	F	3	CHIPRES 0W06 10R J 0402
R2105	Bottom	F	3	CHIPRES 0W06 1KO J 0402
R2106	Bottom	I	3	CHIPRES 0W06 100K J 0402

Item	Side	X	Y	Description
R2107	Bottom	F	4	CHIP VARISTOR VWM14V VC50V 0402
R2108	Bottom	H	3	CHIPRES 0W06 1K0 J 0402
R2109	Bottom	H	3	CHIPRES 0W06 47K J 0402
R2110	Bottom	I	3	CHIPRES 0W06 100K J 0402
R2111	Bottom	H	3	CHIPRES 0W06 100K J 0402
R2114	Bottom	B	2	CHIPRES 0W06 22K J 0402
R2115	Bottom	C	2	CHIPRES 0W06 6K8 J 0402
R2116	Bottom	B	2	CHIPRES 0W06 100K J 0402
R2117	Bottom	B	7	CHIP VARISTOR VWM14V VC50V 0402
R2118	Bottom	C	7	CHIP VARISTOR VWM14V VC50V 0402
R2121	Bottom	F	3	CHIPRES 0W06 4K7 J 0402
R2123	Bottom	C	2	CHIPRES 0W06 6K8 J 0402
R2124	Bottom	B	2	CHIPRES 0W06 22K J 0402
R2125	Bottom	J	3	CHIPRES 0W06 82K F 0402
R2126	Bottom	I	3	CHIPRES 0W06 82K F 0402
R2127	Bottom	J	3	CHIPRES 0W06 33K F 0402
R2128	Bottom	J	3	CHIPRES 0W06 33K F 0402
R2200	Bottom	N	3	CHIPRES 0W25 0R22 J 0805
R2202	Bottom	P	5	CHIPRES 0W06 10K J 0402
R2203	Bottom	I	3	CHIPRES 0W06 4K7 J 0402
R2204	Bottom	P	7	CHIPRES 0W06 4K7 J 0402
R2205	Bottom	P	8	CHIPRES 0W06 100K J 0402
R2206	Bottom	I	3	CHIPRES 0W06 100K J 0402
R2207	Bottom	I	3	CHIPRES 0W06 100K J 0402
R2208	Bottom	M	4	CHIPRES 0W06 27K J 0402
R2400	Top	L	3	CHIPRES 0W06 100K J 0402
R2403	Bottom	C	9	CHIP VARISTOR VWM14V VC50V 0402
R2404	Bottom	E	9	CHIP VARISTOR VWM14V VC50V 0402
R2406	Bottom	R	7	CHIPRES 0W06 10K J 0402
R2407	Bottom	R	7	CHIPRES 0W06 330K J 0402
R2408	Bottom	F	4	CHIPRES 0W06 33R J 0402
R2409	Bottom	F	4	CHIPRES 0W06 12R J 0402

Item	Side	X	Y	Description
R2410	Bottom	F	4	CHIPRES 0W06 470R J 0402
R2411	Top	L	4	CHIPRES 0W06 33R J 0402
R2412	Bottom	E	4	CHIPRES 0W06 10K J 0402
R2413	Bottom	F	4	CHIPRES 0W06 4K7 J 0402
R2414	Top	L	4	CHIPRES 0W06 10K J 0402
R2415	Bottom	E	4	CHIPRES 0W06 4K7 J 0402
R2416	Bottom	E	4	CHIPRES 0W06 4K7 J 0402
R2417	Top	L	4	CHIPRES 0W06 4K7 J 0402
R2418	Bottom	O	8	CHIPRES 0W06 12K J 0402
R2420	Bottom	C	9	CHIP VARISTOR VWM14V VC50V 0402
R2421	Bottom	Q	9	CHIP VARISTOR VWM14V VC50V 0402
R2422	Bottom	Q	9	CHIP VARISTOR VWM14V VC50V 0402
R2423	Bottom	E	4	CHIPRES 0W06 4K7 J 0402
R2424	Bottom	F	4	CHIPRES 0W06 4K7 J 0402
R2425	Top	L	4	CHIPRES 0W06 4K7 J 0402
R2426	Bottom	E	4	CHIPRES 0W06 1K0 J 0402
R2427	Bottom	E	4	CHIPRES 0W06 10K J 0402
R2600	Bottom	N	2	CHIPRES 0W125 4R7 J 0805
R2700	Bottom	R	7	ASIP SIM INTERFACE **low cap** BGA8
R2800	Bottom	C	6	CHIPRES 0W06 4K7 J 0402
R2801	Bottom	C	5	CHIPRES 0W06 4K7 J 0402
R2803	Bottom	O	5	CHIPRES 0W06 100R J 0402
R2804	Bottom	O	5	CHIPRES 0W06 100R J 0402
R2808	Bottom	P	6	CHIPRES 0W06 10K J 0402
R2809	Bottom	P	5	CHIPRES 0W06 10K J 0402
R2900	Bottom	L	3	CHIPRES 0W06 4K7 J 0402
R2901	Bottom	M	8	CHIPRES 0W06 1K0 J 0402
R2902	Bottom	M	8	CHIPRES 0W06 4K7 J 0402
R2904	Bottom	M	6	CHIPRES 0W06 1K0 J 0402
R2905	Bottom	M	7	CHIPRES 0W06 4K7 J 0402
R2906	Bottom	M	6	CHIPRES 0W06 1K0 J 0402
R2907	Bottom	M	7	CHIPRES 0W06 1K0 J 0402

Item	Side	X	Y	Description
R2908	Bottom	H	7	CHIPRES 0W06 4K7 J 0402
R3000	Bottom	P	7	CHIPRES 0W06 47R J 0402
R3001	Bottom	P	6	CHIPRES 0W06 100K J 0402
R3002	Bottom	P	8	CHIPRES 0W06 4K7 J 0402
R3502	Top	M	4	CHIPRES 0W06 4K7 J 0402
R3503	Top	M	4	CHIP VARISTOR VWM14V VC50V 0402
R3504	Top	L	4	CHIPRES 0W06 180R J 0402
R6000	Bottom	O	8	CHIPRES 0W06 47R J 0402
R6100	Bottom	M	9	CHIPRES 0W06 10K J 0402
R6101	Bottom	M	8	CHIPRES 0W06 100K J 0402
R6203	Bottom	B	5	CHIPRES 0W06 100K J 0402
R6252	Bottom	C	2	CHIPRES 0W06 47R F 100PPM 0402
R6600	Bottom	E	6	CHIPRES 0W06 4K7 J 0402
R6601	Bottom	E	6	CHIPRES 0W06 4K7 J 0402
R6604	Bottom	B	6	CHIPRES 0W06 10K J 0402
R6608	Bottom	D	5	CHIPRES JUMPER 0R0 0402
R6619	Bottom	D	5	CHIPRES JUMPER 0R0 0402
R6622	Bottom	C	5	CHIPRES 0W06 47K J 0402
R7001	Bottom	L	9	CHIPRES 0W06 10K J 0402
R7002	Bottom	L	9	CHIPRES 0W06 27K J 0402
R7007	Bottom	L	8	CHIPRES 0W06 22K J 0402
R7008	Bottom	L	8	CHIPRES 0W06 43K 1% 0402
R7009	Bottom	K	8	CHIPRES 0W06 12K J 0402
R7011	Bottom	L	8	CHIPRES 0W06 150R J 0402
R7012	Bottom	L	8	CHIPRES 0W06 180R J 0402
R7100	Bottom	L	5	CHIPRES 0W06 1K0 J 0402
R7101	Bottom	L	5	CHIPRES 0W06 470R J 0402
R7102	Bottom	L	5	CHIPRES 0W06 4K7 J 0402
R7103	Bottom	L	3	CHIPRES 0W06 8K2 J 0402
R7104	Bottom	L	5	CHIPRES 0W06 27K J 0402
R7161	Bottom	H	3	CHIPRES 0W06 47K J 0402
R7162	Bottom	I	3	CHIPRES 0W06 47K J 0402

Item	Side	X	Y	Description
R7163	Bottom	I	3	CHIPRES 0W06 47K J 0402
R7164	Bottom	H	4	CHIPRES 0W06 4R3 J 0402
R7165	Bottom	I	4	CHIPRES 0W06 82R J 0402
R7166	Bottom	I	4	CHIPRES 0W06 4R3 J 0402
R7200	Bottom	K	6	CHIPRES 0W06 10R J 0402
R7201	Bottom	K	6	CHIPRES 0W06 10K J 0402
R7206	Bottom	M	7	CHIPRES 0W06 100R J 0402
R7209	Bottom	L	6	CHIPRES 0W06 10R J 0402
R7210	Bottom	I	6	CHIPRES 0W06 150R J 0402
R7211	Bottom	K	6	CHIPRES 0W06 3K9 J 0402
R7212	Bottom	J	6	CHIPRES 0W06 10K J 0402
R7213	Bottom	J	7	CHIPRES 0W06 10K J 0402
R7215	Bottom	I	7	CHIPRES 0W06 2K2 J 0402
R7216	Bottom	L	6	CHIPRES 0W06 10R J 0402
R7301	Bottom	C	8	CHIPRES 0W06 56R J 0402
R7307	Bottom	C	7	CHIPRES 0W06 56R J 0402
R7308	Bottom	H	8	NTC RES 0W1 47K J B 4050+-3% 0402
R7350	Bottom	F	8	CHIPRES 0W06 100R J 0402
R7352	Bottom	F	8	CHIPRES 0W06 1K8 J 0402
S2401	Bottom	C	9	SM SW TACT SPST 12V SIDE KEY 2.2N
S2402	Bottom	E	9	SM SW TACT SPST 12V SIDE KEY 2.2N
S2403	Bottom	P	9	SM SW TACT SPST 12V SIDE KEY 2.2N
V2000	Bottom	Q	2	ASIP TVS BGA4
V2100	Bottom	G	3	TR NPN AF 30V 0A1 0W1 CSP 1006
V2101	Bottom	H	3	TR NPN AF 30V 0A1 0W1 CSP 1006
V2400	Bottom	R	6	SCH DI MBRM120L 20V 1A POWERMITE
V2401	Bottom	E	4	TR 45V PNP 0A1 0W1 HFE120~ CSP1006
V2402	Bottom	E	4	TR 45V PNP 0A1 0W1 HFE120~ CSP1006
V2403	Bottom	E	4	TR 45V PNP 0A1 0W1 HFE120~ CSP1006
V2404	Bottom	E	4	TR 45V PNP 0A1 0W1 HFE120~ CSP1006
V2405	Top	L	4	TR 45V PNP 0A1 0W1 HFE120~ CSP1006
V2406	Top	L	4	TR 45V PNP 0A1 0W1 HFE120~ CSP1006

Item	Side	X	Y	Description
V2407	Top	L	4	TR 45V PNP 0A1 0W1 HFE120~ CSP1006
V2408	Bottom	E	4	TR NPN AF 30V 0A1 0W1 CSP 1006
V2409	Bottom	E	4	TR NPN AF 30V 0A1 0W1 CSP 1006
V2410	Top	L	4	TR NPN AF 30V 0A1 0W1 CSP 1006
V2411	Top	R	7	LED WHITE 90-345MCD 10MA 90DEG
V2413	Top	R	4	LED WHITE 90-345MCD 10MA 90DEG
V2900	Bottom	M	8	TR NPN AF 30V 0A1 0W1 CSP 1006
V2901	Bottom	M	7	TR NPN AF 30V 0A1 0W1 CSP 1006
V2902	Bottom	M	6	TR NPN AF 30V 0A1 0W1 CSP 1006
V3500	Top	L	4	TRX2 N 40V 0A1 GENERAL PURPOSE SOT666
V7100	Bottom	L	5	CAP.DI BBY57-02W 1/4 16/4P SOD523
X0001	Top	K	2	MODULE ID COMPONENT 2.8X1.8X0.3
X2000	Bottom	G	8	SM BATTERY CONN 3POL SPR 12V 2A
X2001	Bottom	S	6	SM SYSTEM CONNECTOR 14POL
X2100	Bottom	E	3	CONN AUD 4POL SMD 12V 1A 2.5MM DIA
X2700	Bottom	Q	7	SM SIM CONN 6POL P2.54 H1.5
X3500	Top	L	7	CONN BTB 2X25M P0.4 30V 0.3A
X6250	Bottom	D	3	SM COAX CONN+SW F 50R 250V 6GHZ
X6251	Bottom	D	2	CONN POGO 2 PIN 6.6X3.7X2.5
X6600	Bottom	F	5	SM CAMERA MOD SKT 2X8F
X6601	Bottom	G	3	CONN POGO 2 PIN 6.5X5.4X2.3MM
X7300	Bottom	B	9	SM COAX CONN+SW F 50R 250V 6GHZ
Z2100	Bottom	P	3	ASIP AUDIO OUTPUT STAGE
Z2101	Top	S	6	ASIP AUDIO MICROPHONE INPUT STAGE
Z2102	Bottom	P	3	ASIP AUDIO OUTPUT STAGE
Z2103	Bottom	F	3	ASIP AUDIO MICROPHONE INPUT STAGE
Z2104	Bottom	P	4	ASIP AUDIO OUTPUT STAGE
Z2105	Bottom	S	2	ASIP AUDIO MICROPHONE INPUT STAGE
Z2400	Top	K	9	ASIP KEYBOARD INTERFACE *PB-FREE*
Z6000	Bottom	R	3	LTCC FILT 2441.75+-41.75MHZ 2.0X1.5
Z6250	Bottom	D	3	CER FILT 1575.42+-40MHZ 3.6X3.6
Z7000	Bottom	J	8	SAW FILT 836.5+-12.5MHZ/2.5 2X1.6

Item	Side	X	Y	Description
Z7001	Bottom	J	8	SAW FILT 1850-1910MHZ 2X1.6X0.68
Z7160	Bottom	H	5	SAW FILT 881.52 MHz 2X1.6X0.8
Z7161	Bottom	H	4	SAW FILT 1960+-30MHz/3.5dB 2x1.6
Z7162	Bottom	J	5	XTAL FILT 128.1MHZ/4DB 3X3X1
Z7163	Bottom	J	4	SAW FILT 128.1MHZ 7X5X1.48
Z7300	Bottom	D	8	DUPL 1930-1990/1850-1910MHZ 5X5
Z7301	Bottom	C	8	DIPL 1850-1990/824-894MHZ
Z7302	Bottom	D	7	DUPL 824-849/869-894MHZ 3.8X3.8X1.5

This page intentionally left blank.