



## Next Generation High Performance GNSS Receiver

### Benefits

Innovative OEM6™ technology

Supports current and future GNSS signals

Application-based configurations

Designed for rapid integration

### Features

Low power consumption

Flexible communication interfaces

Software configurable performance

Ultralight

High position accuracy and availability

SPAN INS functionality

### Designed with the Future in Mind

The OEM628 is designed with NovAtel's new 120 channel ASIC, which tracks all current and upcoming Global Navigation Satellite System (GNSS) constellations and satellite signals including GPS, GLONASS, Galileo and Compass. Configurable channels optimize satellite availability in any condition, no matter how challenging. Already tracking GPS L5 and Galileo GIOVE-A/B test satellites, the OEM6 is software upgradable to track future signals as they become available. Maximizing satellite availability and optimizing GNSS signal usage now, and in the future, ensures consistent, high performance GNSS positioning.

### Easy System Integration

The OEM628 is designed and built with a focus on product quality and ease of integration. It maintains our industry setting OEM-V2 form factor, ensuring a successful drop-in replacement fit, with backward compatible command and log interface for existing customers. A development kit and user friendly configuration software is available to assist new customers with rapid integration and faster time to market. NovAtel's well established, comprehensive set of software commands facilitates system integration. Ethernet and NTRIP 2.0 Client and Server connectivity is offered in addition to our traditional communications interfaces.

### Flexible Configurations for your Application

Proven and innovative new NovAtel technology combine to achieve the best in GNSS positioning. NovAtel's industry leading Pulse Aperture Correlator (PAC) multipath mitigation technology is standard and ensures the highest quality measurements and positioning. Innovative new technology provides excellent resistance to interference for consistent, accurate and reliable positioning. Configurable options ensure your positioning and accuracy needs are always met. To learn more about how our firmware options can enhance your positioning, please visit [www.novatel.com/products/firmware-options](http://www.novatel.com/products/firmware-options).

If you require more information about our receivers, visit [novatel.com/products/gnss-receivers/oem-receiver-boards](http://novatel.com/products/gnss-receivers/oem-receiver-boards)

[novatel.com](http://novatel.com)

[sales@novatel.com](mailto:sales@novatel.com)

1-800-NOVATEL (U.S. and Canada)

or 403-295-4900

China 0086-21-54452990-8011

Europe 44-1993-848-736

SE Asia and Australia 61-400-883-601



## Performance<sup>1</sup>

### Channel Configuration

120 Channels<sup>2</sup>  
 Signal Tracking  
 GPS: L1, L2, L2C, L5  
 GLONASS: L1, L2  
 Galileo: E1, E5<sup>3</sup>  
 GIOVE-A/GIOVE-B (test)  
 Compass<sup>4</sup>  
 SBAS  
 QZSS  
 L-Band

### Horizontal Position Accuracy (RMS)

Single point L1	1.5 m
Single point L1/L2	1.2 m
SBAS <sup>5</sup>	0.6 m
DGPS	0.4 m
L-Band	
VBS	0.6 m
XP	0.15 m
HP	0.1 m
RT-2™	1 cm+1 ppm
Initialization time	<10 s
Initialization reliability	> 99.9%

### Measurement Precision (RMS)

Fully independent code and carrier measurements:

	GPS	GLO
L1 C/A code	4 cm	8 cm
L1 carrier phase	0.5 mm	1.0 mm
L2 P(Y) code <sup>6</sup>	8 cm	8 cm
L2 carrier phase <sup>6</sup>	1.0 mm	1.0 mm
L2C code <sup>7</sup>	8 cm	8 cm
L2C carrier phase <sup>7</sup>	0.5 mm	0.5 mm
L5 code	3 cm	-
L5 carrier phase	0.5 mm	-

### Maximum Data Rate<sup>8</sup>

Measurements	100 Hz
Position	100 Hz

### Time to First Fix

Cold start <sup>9</sup>	<50 s
Hot start <sup>10</sup>	<35 s

### Signal Reacquisition

L1	<0.5 s (typical)
L2	<1.0 s (typical)

**Time Accuracy<sup>11</sup>** 20 ns RMS

**Velocity Accuracy** 0.03 m/s RMS

**Velocity<sup>12</sup>** 515 m/s

## Physical and Electrical

**Dimensions** 60 x 100 x 9.1 mm

**Weight** 37 g

### Power

Input voltage <sup>13</sup>	+3.3 VDC [+5%/-5%]
Power consumption <sup>14</sup>	1.3 W

### Antenna LNA Power Output

Output voltage	5 VDC [±5%]
Maximum current	100 mA

### Connectors

Main	24-pin dual row male header
Aux	16-pin dual row male header
Antenna input	MMCX female
External oscillator input	MMCX female

## Communication Ports

1 RS-232	up to 921,600 bps
2 LVTTL	up to 921,600 bps
2 CAN Bus <sup>14</sup>	1 Mbps
1 USB port	12 Mbps
1 LAN Ethernet port supporting:	
-10BaseT/100BaseT networks	
-Direct TCP/IP & UDP connectivity	
-NTRIP (v2.0) client and server	

Pulse per second output  
 Event marker input support

## Environmental

### Temperature

Operating	-40°C to +85°C
Storage	-40°C to +85°C

**Humidity** 95% non-condensing

### Vibration

Random vibrate	MIL-STD 810G (Cat 24, 7.7 g RMS)
Sine vibrate	IEC60068-2-6

**Bump** IEC9022-31-06 (25 g)

**Shock** MIL-STD-810G (40g)  
 Survival (1000g)

## Features

- Field upgradeable software
- 20 Hz measurement and position data rate
- PAC multipath mitigating technology
- Differential GPS positioning
- Differential correction support for RTCM 2.1, 2.3, 3.0, 3.1, CMR, CMR+ and RTCA
- Navigation output support for NMEA-0183 and detailed NovAtel ASCII and binary logs
- Auxiliary strobe signals, including a configurable 1 PPS output for time synchronization and mark inputs
- Outputs to drive external LEDs
- External oscillator input

## NovAtel Connect

NovAtel Connect is an intuitive configuration and visualization tool suite allowing comprehensive control of the OEM628 product.

- Easy to use wizards guide you through positioning mode configuration and raw data collection
- Detailed graphical windows display comprehensive status information
- Plan view and playback files allow you to monitor the positioning and configuration history
- Remotely control and monitor the OEM628 over the internet
- Available on Windows XP, Windows 7 and Linux platforms

## Firmware Options

- RT-2
- L-Band
- ALIGN®
- GL1DE®
- RAIM
- 100 Hz output rate<sup>8</sup>
- SPAN®

## Additional Accessories

- GPS-700 series antennas
- ANT series antennas
- RF cables—5, 10 and 30 m lengths
- OEM6 Development Kit



Version 6 - Specifications subject to change without notice.

© 2012 NovAtel Inc. All rights reserved.

NovAtel, GL1DE and ALIGN are registered trademarks of NovAtel Inc.

RT-2, OEM6 and OEM628 are trademarks of NovAtel Inc.

Printed in Canada.

OEM628 September 2012 D15588

For the most recent details of this product:

[novatel.com/assets/Documents/Papers/OEM628.pdf](http://novatel.com/assets/Documents/Papers/OEM628.pdf)

<sup>1</sup> Typical values. Performance specifications subject to GPS system characteristics, US DOD operational degradation, ionospheric and tropospheric conditions, satellite geometry, baseline length, multipath effects and the presence of intentional or unintentional interference sources.

<sup>2</sup> Tracks up to 60 L1/L2 satellites.

<sup>3</sup> Includes ESa, ESb and Alt-BOC.

<sup>4</sup> The Compass signal is not finalized and changes in the signal structure may still occur. Designed for Compass Phase 2 and 3, B1 and B2 compatibility.

<sup>5</sup> GPS only.

<sup>6</sup> L2 P for GLONASS.

<sup>7</sup> L2 C/A for GLONASS.

<sup>8</sup> 100 Hz while tracking up to 20 satellites.

<sup>9</sup> Typical value. No almanac or ephemerides and no approximate position or time.

<sup>10</sup> Typical value. Almanac and recent ephemerides saved and approximate position and time entered.

<sup>11</sup> Time accuracy does not include biases due to RF or antenna delay.

<sup>12</sup> Export licensing restricts operation to a maximum of 515 metres per second.

<sup>13</sup> Consult the *OEM6 Family Installation & Operation* user manual for power supply considerations.

<sup>14</sup> Power consumption values for GPS L1/L2 with Ethernet disabled.

<sup>15</sup> User application software required.

