AUDIO SIGNAL PATH

L7302 1u
C7302 6V100
X7302 VSX0953
C7316 0.1
R7327 8200
R7325 0

TEST1 (22) 3.3
VDDA2 (21)
VSSA2 (20)
VDDR2 (19)
1 REF (18) 2.0
TEST2 (17)
TP3 (16)
XTAL I (15) 1.6
XTAL O (14) 1.6
ADDR1 (13)
PCLK (12) 0.4

SIF2 (23) 2.0
C7315 0.1
VREF1 (24) 2.0
SIF1 (25) 2.0
CRESET (26) 4.9
VSSA3 (27)
VDDA3 (28) 4.9
SCL (29) 4.8
SDA (30) 4.6
SDO (31) 1.2
WS (32) 1.2
SCK (33) 1.2

INPUT SWITCH AGC, ADC
FM/AM DEMODULATION
IDENTIFI-CATION
IIC BUS INTERFACE
IIC BUS INTERFACE
NICAM DEMODULATION
DEMATRIX
NICAM DECODER
2 CHANNEL ANALOG/ SATELLITE DECODER
DIGITAL SELECTOR
LEVEL ADJUST
POST FILTER 3 DACS
2 CHANNEL OUTPUT BUFFERS
ANALOG CROSSBAR SWITCH
MONO CHANNEL OUTPUT BUFFERS

TP1 (11)
NICAM (10) 0.4
TP2 (9)
VDEC2 (8) 0
VSSD2 (7)
VDDD1 (6) 4.8
VSSD1 (5)
VSSA1 (4)
VDDA1 (3) 4.9
OUT R (2) 2.5
OUT L (1) 2.5

SYS CLK (34) 1.2
VDDD3 (35) 4.8
VSSD3 (36)
P1 (37) 4.9
MONO IN (38) 2.4
EXTIR (39) 2.4
EXTIL (40) 2.4
VREF2 (41) 2.4
P2 (42) 4.9
OUT M (43) 2.5
VSSA4 (44)

IC7301
TDA9874AH

LB7301 0
C7325 0.1
C7324 0.1

R7316 10K
LB7303 0
TL7301
TL7303
C7313 0.1
C7318 6V47
TL7304
R7324 220
C7317 16V10
R7328 220
C7319 16V10
R7329 220
C7320 16V10

PK7301
TO POWER SUPPLY/RF SECTION PK7301 (C-10)
1 QPSK/SIF 1.6
2 GND
3 TUNER AUDIO (N) 0
4
5
6
7 TUNER 5V 4.9

C7307 0.01
R7302 0
C7311 0
L7301 0

IC7302
PST7043
(RESET)
IN (1) 4.9
GND (2)
OUT (3) 4.9

C7308 50V2.2
C7312 0.1
R7305 100
R7306 100
C7305 33P
C7306 33P

PK7302
TO POWER SUPPLY/RF SECTION PK7302 (B-10)
1 SYS IIC CLOCK 4.8
2 SYS IIC DATA 4.6
3
4 TUNER AUDIO (R) 0
5 GND
6 TUNER AUDIO (L) 0

FL7301 VLF0633
C7304 6V100
C7301 0.01
(E/F)
C7303 0.01
(C/D)
C7341 4700P
C7342 4700P

NOTE:THE MEASUREMENT MODE OF THE DC VOLTAGE ON THIS DIAGRAM IS STOP MODE.

NOTE: DO NOT USE ANY PART NUMBER SHOWN ON THIS SCHEMATIC DIAGRAM FOR ORDERING. WHEN YOU ORDER A PART,PLEASE REFER TO PARTS LIST.