

No.	NAME	I/O	Description		P-OFF	P-SAVE	P-FAIL	Reset															
1	CURRENT_LIMIT	O	Current limit terminal for Capstan driver.		Low	Low	Low	Low															
2	F ADJUST	O	Analogue voltage output for Head frequency response adjustment.		Low	Low	Low	Low															
3	SCAS_IN(L)	I	Detection Terminal for VHS tape or S-VHS tape.		In	In	In	In															
4	ADUB(H)	O	Switching terminal of BIAS OSC noise reduction filter in ADUB (1). The VCR mode is ADUB/ADUB-PS(Including Assemble/Synchro./AV Insert): High output (2). Other than above: Hi-Z output		Hi-Z	Hi-Z	Hi-Z	Hi-Z															
5	TRACKING_ENVE	I	Video envelope input terminal for auto tracking and CVC.		In	In	In	In															
6	SLP(H)	O	Tape speed output terminal.(EE/VV) *When the NTSC10/PAL9H is set up as the Servo data.: High (H) output. *Other than above speed : Low (L) output.		Low	Low	Low	Low															
7	LP(H)	O	Tape speed output terminal.(EE/VV) *When the NTSC4H/6H or PAL6H/9H is set up as the Servo data : High (H) Output. *Other than above speed : Low (L) output. *As for 2 head model, the output signal is fixed to low, no matter if it has LP mode or not.		Low	Low	Low	Low															
8	CPB	I	PB(H) input terminal from AV2. *From 3.85v to 5.0v : High *From 1.82v to 2.84v :Middle *From 0v to 0.81v :Low		In	In	In	In															
9	AFC_S	I	S curve input terminal from the Tuner.		In	In	In	In															
10	A-MUTE(H)	O	Audio mute signal exclusive for the RF converter.		High	High	Low	High															
11	AV1_8IN	I	PB(H) input terminal from AV1. *From 3.85v to 5.0v : High *From 1.82v to 2.84v :Middle *From 0v to 0.81v :Low		In	In	In	In															
12	N/S/T2/T3	I	Normal/Service/Test2/Test3 select *Over than 4.0v :NORMAL mode *From 2.5v to 4.0v :SERVICE mode *From 1.0v to 2.5v :TEST2 mode *From 0v to 1.0v :TEST3 mode		In	In	In	In															
13	S-PHOTO	I	Tape end sensor input from supply side. *More than 2.6V: Black / Less than 2.4V : white)		In	In	In	In															
14	T-PHOTO	I	Tape beginning sensor input from take up side *More than 2.6V: Black / Less than 2.4V : white)		In	In	In	In															
15	ABS_NORM(H)	I	Input terminal for FM audio envelope level detection.		In	In	In	In															
16	S-VHS/MES/NOR	I	Input terminal for Playback detection result. (S-VHS/MESECAM/NORMAL)		In	In	In	In															
17	S-VHS(H)	O	Output terminal for S-VHS mode.		Low	Low	Low	Low															
18	SECAM_ID_IN(L)	I	Input terminal for SECAM detection result.		In	In	In	In															
19	D.FM.REC(H)	O	Control signal for timing of FM audio recording current.		Low	Low	Low	Low															
20	ART.V/H/N	O	Output terminal of the Artificial V synchronization signal.		Low	Low	Low	Low															
21	AV1_OUT_SW(L)	I	Input terminal of composite/component switching for AV1 output. *It is automatically switched composite/component when this result is sent to TV using P50.		In	In	In	In															
22	AV3_S_IN(L)	I	Input terminal of AV3_S-VHS input condition. *AV3_S-VHS IN : "Low" (L).		In	In	In	In															
23	ET_REC(H)	O	REC Mode output terminal of the S-VHS-ET.		Low	Low	Low	Low															
24	VIDEO.H.SW	O	Output terminal for video HEAD switching signal.		Low	Low	Low	Low															
25	A.H.SW	O	Output terminal for FM audio HEAD switching signal.		Low	Low	Low	Low															
26	A.DEF(H)	O	Output terminal for decoder IC Reset.		Low	Low	Low	Low															
27	TBC MODE0	O	TBC MODE0 output.		Low	Low	Low	Low															
28	AVPB-H(L)	O	Output terminal of PB (H/M) for AV2. (If the unit has only one scart terminal, this is for AV1.) *To be outputted signal from 21pin (8) has been changed to H/M/L signal in accordance with the following terminal's settings.		High	High	Low	High															
29	AVPB-M(H)	O	<table border="1"> <tr> <td>pin8</td> <td>Setting</td> <td>AVPBH-(L)</td> <td>AVPBM-(H)</td> </tr> <tr> <td>High</td> <td>L</td> <td>Hi-Z</td> <td></td> </tr> <tr> <td>Middle</td> <td>H</td> <td>Hi-Z</td> <td></td> </tr> <tr> <td>Low</td> <td>H</td> <td>L</td> <td></td> </tr> </table>					pin8	Setting	AVPBH-(L)	AVPBM-(H)	High	L	Hi-Z		Middle	H	Hi-Z		Low	H	L	
pin8	Setting	AVPBH-(L)	AVPBM-(H)																				
High	L	Hi-Z																					
Middle	H	Hi-Z																					
Low	H	L																					
30	GND(D)	I	GND		---	---	---	---															
31	20MHz.IN	I	Main oscillator input		---	STOP	STOP	---															
32	20MHz.OUT	O	Main oscillator output		---	STOP	STOP	---															
33	+5V(D)	I	VDD		---	---	---	---															
34	32KHz IN	I	Sub oscillator input		---	---	---	---															
35	32KHz OUT	O	Sub oscillator output		---	---	---	---															
36	VCONT	I	Open		---	---	---	---															