



DA051010 5/10 MHz Distribution Amplifier



General Description

The DA051010 can be used to synchronize up to twelve instruments to a frequency reference input. The reference input frequency is 5 MHz and the output frequency is 10 MHz. The DA051010 incorporates AGC (automatic gain control) so that a 5 MHz input can be varied from -10 dBm to +20 dBm without the outputs changing by more than 0.4 dB. Inputs as low as -30 dBm still produce a useable output. The pure sinewave output (harmonics are 65 dB down) enables the DA051010 to work in the most demanding applications. The DA051010 can also accept an input frequency of 10 MHz.

Outputs

There are ten, 10 MHz, sinewave outputs. Each 10 MHz output is isolated from the input and each other. Therefore the reference oscillator connected to the DA051010 input is protected against load variations, short circuits etc. that may be applied to the outputs. Two additional squarewave outputs can be switched in frequency from 10 MHz, 5 MHz, 2 MHz, 1 MHz, 100 kHz and 1 Hz. These outputs are ideal for instruments that do not use a 10 MHz timebase. A rear slave output can be connected to a second DA051010 (or more) to give up to twenty-four outputs (or more). See "Applications" below.

Applications

The DA051010 5/10 MHz Distribution Amplifier is ideal for use in calibration or standard laboratories, radio repair workshops or production facilities. By using the rear slave output, many DA051010's can be connected together to give multiple outputs

Miscellaneous Information

The DA051010 is a highly reliable unit with an MTBF of over 30 years. The DA051010 is housed in a fully screened 19" rack mount case and operates from a 115 VAC or 230 VAC supply or external 12 V DC. The DA051010 is CE marked for sale within the EEC.

Options

The DA series can be modified upon special request to work at different frequencies than 10 MHz. For example the DA151510 accepts a 15 MHz input and has 15 MHz outputs. Other frequencies to 20 MHz can also be accommodated.

Option 01 is an Alarm Relay that is activated when the 5 MHz input signal is present. Two changeover relay contacts can be used to raise an alarm should the input signal or power be lost. Two logic outputs also show the alarm status.

Option 02 is a redundancy option allowing two DA051010's to be operated in parallel giving a fully redundant output. A typical system consists of two Frequency Standards ("A" and "B") and two DA051010 distribution amplifiers ("A" and "B"). The system would have twenty redundant outputs. Normally the "A" pair will provide the 10 MHz output. In the

event of a failure of the Frequency Standard (“A”) or DA051010 (“A”), the “B” system would automatically switch in and provide the 10 MHz output.

DA051010 SPECIFICATIONS

Specification Parameter	Specification	Comments	
Input			
Frequency	5.000 MHz or 10.000 MHz	50 Ω BNC Connector on rear panel	
Bandwidth (-3 dB) 5 MHz input	125 kHz		
Impedance	50 Ω		
Input VSWR	< 1.15 @ 5 MHz and 10 MHz		
Input Level	+20 dBm to -10 dBm	Output Changes by < 0.4 dB	
Sinewave Outputs 1 to 10			
Output Waveform	Sinewave	50 Ω BNC Connector on rear panel	
Output Frequency (5 MHz input)	Exactly twice the input frequency		
Output Frequency (10 MHz input)	Exactly the same as the input frequency		
Output VSWR	< 1.5:1 @ 10 MHz		
Output level (output 5,7,9,11,13)	From 0 dBm to +13 dBm	Each output internal adjustable	
Output level (output 4,6,8,10,12)	From 0 dBm to +10 dBm	Each output internal adjustable	
Harmonic Distortion at 10 MHz	-65 dBc	Output set to +10 dBm	
Jitter	< 2 ps rms		
5 MHz sub-harmonic rejection	-35 dBc	Sine Outputs 1,3,5,7,9	
5 MHz sub-harmonic rejection	-60 dBc	Sine Outputs 2,4,6,8,10	
Input to Output Isolation	> 100 dB	Typical@ 10 MHz	
Squarewave Outputs 1 and 2			
Output Waveform	Squarewave	50 Ω BNC Connector on rear panel	
Level	0 - 5V (open circuit) 0 - 2.7 V (50 Ω)	TTL Compatible	
Frequency	10,5,2,1 MHz, 100 kHz and 1 Hz	1 Hz = 1 pulse per second	
Risetime	< 30 ns	At 1 MHz	
Slave Output			
Output Waveform	Sinewave @ > -5 dBm	50 Ω BNC Connector on rear panel	
Phase Noise (Typical)			
At 10 Hz Offset	-127 dBc/Hz	Measurement uncertainty ± 4 dB	
General			
Power (AC)	115 VAC or 230 VAC ± 10%	30 Watts max	
Power (DC)	11-13 VDC @ 1.3 Amps		
Size and weight	483 x 300 x 44 mm and 4.6 kg	Width x Depth x Height	
Ambient Operating Temperature	0°C to +40 °C		
Options			
Option 01	Dual changeover alarm relay contacts	Plus two 8V logic alarm outputs	
Option 02	Redundancy	Requires two units	
Option 03	Internal Backup 10 MHz oscillator	Activated if input signal is lost	
Precision Test Systems			
Head Office - UK	South Africa	USA	Represented locally by:
Precision Test Systems LTD 40 Holkham Avenue, South Woodham Ferrers Essex, CM3 7AU, England Tel: +44 (0) 845 052 0920 Fax: +44 (0) 870 135 4973 Email: uksales@ptsyst.com Web: www.ptsyst.com	Precision Test Systems cc 183 Edison Crescent Hennops Park X7 Pretoria South Africa Tel: +27 (0) 12 653 5848 Email: sasales@ptsyst.com Web: www.ptsyst.com	Precision Test Systems Suite # 981 14781 Memorial Dr. Houston, TX 77079 Tel: 1 888 876 4804 Fax: 1 413 410 1112 Email: usasales@ptsyst.com Web: www.ptsyst.com	

Full specifications available from www.ptsyst.com. Specifications and features subject to change without notice (220805)