



## Active Loudspeaker Box R&S® GA3005

Loudspeaker with through-connection to handset/headset R&S® GA3001/GA3002

The active loudspeaker box is used for loud monitoring of the received signal and can be connected directly to the audio interface of R&S® MR3000 transceivers or the audio connector of the switching unit.

The R&S® GA3005 consists of a loudspeaker box with built in audio amplifier and a box holder, which allows change of the position of the box when necessary. Additionally it features an output for the handset R&S® GA3001 or the headset R&S® GA3002. This allows operation of the loudspeaker together with a handset/headset at the same time.

### Main features

- ◆ no separate power supply required
- ◆ built in audio amplifier
- ◆ output for handset or headset
- ◆ volume control

## Specifications

Power supply voltage	from transceiver
Output power	2 W/8 Ω
<b>Gain</b>	14 dB max.
Power supply	13,8 V to 24 V DC 300 mA max.
Effective frequency range	160 Hz to 3200 Hz
Volume control	continuous
Operating temperature range	-45 °C to +60 °C
Protection provided by enclosure	IP 54
Dimensions (W × H × D)	120 mm × 120 mm × 75 mm
Weight	app. 1.7 kg

## Ordering information

Designation	Type	Order No
Loudspeaker, 2 m cable	R&S® GA3005	6137.7537.02
Loudspeaker, 5 m cable	R&S® GA3005	6137.7537.05
Loudspeaker, 10 m cable	R&S® GA3005	6137.7537.10



More information at  
[www.rohde-schwarz.com](http://www.rohde-schwarz.com)  
 (search term: M3TR)



[www.rohde-schwarz.com](http://www.rohde-schwarz.com)

Europe: +49 1805 12 4242, [customersupport@rohde-schwarz.com](mailto:customersupport@rohde-schwarz.com)  
 USA and Canada: +1-888-837-8772, [customer.support@rsa.rohde-schwarz.com](mailto:customer.support@rsa.rohde-schwarz.com)  
 Asia: +65 65 130 488, [customersupport.asia@rohde-schwarz.com](mailto:customersupport.asia@rohde-schwarz.com)