



ROHDE & SCHWARZ

Test and Measurement
Division

Release Notes

cdma2000/1xEV-DV

Mobile Station Test

Application Firmware R&S FS-K83

Release 4.40

for R&S FSP, FSU, FSQ, FSG, FSMR, FSUP
Analyzer Firmware 4.4x

Release Note Revision: 1

Printed in the Federal
Republic of Germany

Contents

History	3
General Topics	3
Compatibility of R&S FS-K83 cdma2000/1xEV-DV MS Firmware	3
Firmware Update of R&S FS-K83 cdma2000/1xEV-DV MS Firmware	4
Enabling the Application Firmware via License Key Code Entry	4
New Functions in version 4.40	5
Modified Functions.....	5
Problems Eliminated	6
Known Problems	6
Modifications to the Operating Manual	6
Modified Chapters	6
Appendix: Contact to our hotline.....	7

History

Date	Rel Note Rev	Changes
August 18, 2008	1	First revision for R&S FS-K83 Firmware 4.40.

General Topics

Compatibility of R&S FS-K83 cdma2000/1xEV-DV MS Firmware

The following table shows the compatible version of the basic analyzer firmware version and the cdma2000/1xEV-DV MS application firmware:

Table of compatible versions:

R&S FS-K83 Application Firmware	R&S FSP Basic Firmware	R&S FSU Basic Firmware	R&S FSQ Basic Firmware	R&S FSMR Basic Firmware	R&S FSUP Basic Firmware	R&S FMU Basic Firmware	R&S FSG Basic Firmware
4.40	4.40	4.41	4.45	-	-	-	4.49
4.30	4.30	4.31	4.35	-	-	4.38	4.39
4.21	4.20	4.21	4.25	-	4.27	-	4.29 SP1
4.20	-	-	-	-	-	-	4.29
4.10	4.10	4.11	4.15	-	4.17	-	-
4.00	4.00	4.01	4.05	-	-	-	-
3.90	3.90	3.91	3.95	3.96	3.99	-	-
3.80	3.80	3.81	3.85	3.86	-	-	-
3.70	3.70	3.71	3.75	-	-	-	-
3.60	3.60	3.61	3.65	3.66 SP1	-	-	-
3.50	3.50	3.51	3.55	-	-	-	-
3.40	3.40	3.41	3.45	-	-	-	-
3.30	3.30	3.31	3.35	-	-	-	-
3.28	3.20	3.21	3.25	-	-	-	-
3.24	3.10	3.11	3.15	-	-	-	-
2.80	2.80	2.81	-	-	-	-	-
2.60	2.60	2.61	-	-	-	-	-
2.40	2.40	2.41	2.45	-	-	-	-
2.30	2.30	2.31	2.35	-	-	-	-
2.28	2.20	2.21	2.25	-	-	-	-
2.24	2.10	2.11	2.15	-	-	-	-

Application firmware versions 3.xx are running on R&S FSPs with order # 1164.4391.xx or R&S FSU with order # 1166.1660.xx or R&S FSQ with operating system XP.

Application firmware version 2.xx are running on R&S FSPs with order # 1093.4495.xx or R&S FSU with order # 1129.9003.xx or R&S FSQ with operating system NT.

Firmware Update of R&S FS-K83 cdma2000/1xEV-DV MS Firmware

Since basic firmware version 4.2x a ZIP file with the update sets of the basic system firmware and all available applications is provided. This ZIP file is available in the instruments FIRMWARE section, e.g. R&S FSU of the Service Board on GLORIS.

Please follow the steps described in the instrument's basic firmware release note to perform a complete firmware update.

Enabling the Application Firmware via License Key Code Entry

This section can be skipped if the option key was entered once.

After installing the application firmware package a license key for validation must be entered. The license key is printed either on a label on the rear panel of the analyzer or delivered as a part of the R&S FS-K83 cdma2000/1xEV-DV MS application firmware package.

The key sequence for entering the license key is:

SETUP - GENERAL SETUP – OPTIONS - INSTALL OPTION

Use the numeric keypad to input the license key number and press ENTER.

- On a successful validation the message 'option key valid' will appear.
- If the validation failed, the application firmware is not installed.
The most likely reason will be that the instrument is not equipped with the correct basic firmware version. In this case a message box will appear asking for installation of the correct basic firmware version.

If the application firmware package was not installed prior to entering the license key code, a message will appear asking for installation of the application firmware package.

In any case please make sure that the correct basic firmware version and the application firmware package is installed prior to entering the license key code.

New Functions in version 4.40

None.

Modified Functions

The version numbers in brackets indicate the version in which the function was modified

1. [V3.28/V2.28] Unit circle display in constellation diagrams.
2. [V3.28] option FS-K9 power sensor support for RF measurements.
3. [V3.30/V2.30] The FS-K83 can now also analyze Agilent's ESG opt 101 non standard signals.
4. [V3.30/V2.30] Read out of spectrum emission mask worst fail position.
5. [V2.40/3.40] Sign change for frequency offset, phase offset and q-inversion for symbol constellation and bitstream.

Due to a correction of the cdma2000 specific $-q$ definition, the mentioned values had been changed

6. [V3.50] Maximal capture length is increased to 64 for R&S FSU and R&S FSQ. On R&S FSQ also up to 38 sets of 64 PCGs are possible.

7. [V3.50] Command: [SENSe:] CDPower:ORDER? delivers now short form HAD or BTR as result .

8. [V3.60/2.60] Changed SCPI commands

In order to limit to 12 chars the :CALCulate2:FEED 'XTIME:CDPower:SYMBOL:CONStellation' and :CALCulate2:FEED 'XTIME:CDPower:COMPOSITE:CONStellation' are changed to :CALCulate2:FEED 'XTIME:CDPower:SYMBOL:CONSt' and :CALCulate2:FEED 'XTIME:CDPower:COMPOSITE:CONSt'.

9. [V3.60/V2.60] External trigger level adjustable from 0.5 to 3.5V.
10. [V3.60/V2.60] Carrier frequency step size softkey available.
11. [V3.70/V2.80] ACP: number of adjacent channels increased to 12.
12. [V3.70/V2.80] ACP: power mode to max holds the power results.
13. [V3.80/V2.80] Trace view available within code domain analyzer.
14. [V4.00] Spectrum emission mask: List evaluation in lower screen now supported.
15. [V4.20] Support for instrument R&S FSG.
16. [V4.20] Softkey REF VALUE Y AXIS available for CDP measurements.
17. [V4.21] Band Classes 14 and 15 supported.
18. [V4.30] Softkey AC / DC Coupling available.
19. [V4.30] New Ref Value Y Axis / Reference Level coupling simplifies grid scaling configuration for Code Domain measurements.

Since version 4.20 the Reference Level and the grid scaling (REF VALUE Y AXIS) with unit dBm can be independently set for Code Domain measurements. In previous versions changing the Reference Level and changing the Ref Value Y Axis were independent. If the Reference Level value is changed the Ref Value Y Axis is now automatically adjusted to keep the difference between Reference Level and Ref Value Y axis constant.

Example:

Ref Level set to 0 dBm

Ref Value Y axis set to -10 dBm (at Y Axis Position 100%)

► The upper Y limit of the grid scaling is now at 10 dB below reference level.

Change Reference Level to -10dBm

The Ref Value Y Axis is now adjusted to -20 dB

► The upper Y limit of the grid scaling is at 10 dB below reference level as before.

Note: The internal reference level change with function ADJUST REF LEVEL is treated in the same way.

Problems Eliminated

None.

Known Problems

None.

Modifications to the Operating Manual

For the R&S FS-K83 cdma2000/1xEV-DV MS Application Firmware manuals please refer to the following order numbers:

- 1007.9800.44-05 (German/English)

They can be downloaded from R&S internet – search: FS-K83:

<http://www.rohde-schwarz.com>

Modified Chapters

None.

Appendix: Contact to our hotline

Any questions or ideas concerning the instrument are welcome by our hotline:

USA & Canada

Monday to Friday (except US public holidays)
8:00 AM – 8:00 PM Eastern Standard Time (EST)
Tel. from USA 888-test-rsa (888-837-8772) (opt 2)
From outside USA +1 410 910 7800 (opt 2)
Fax +1 410 910 7801
E-mail Customer.Support@rsa.rohde-schwarz.com

East Asia

Monday to Friday (except Singaporean public holidays)
8:30 AM – 6:00 PM Singapore Time (SGT)
Tel. +65 6 513 0488
Fax +65 6 846 1090
E-mail Customersupport.asia@rohde-schwarz.com

Rest of the World

Monday to Friday (except German public holidays)
08:00 – 17:00 Central European Time (CET)
Tel. from Europe +49 (0) 180 512 42 42
From outside Europe +49 89 4129 13776
Fax +49 (0) 89 41 29 637 78
E-mail CustomerSupport@rohde-schwarz.com