

CPD-200ES

SERVICE MANUAL

CPD-200ES
S. Hemisphere Model
Equator Model

Chassis No. SCC-L16B-A



X2F CHASSIS

SPECIFICATIONS

Picture Tube	0.26 mm aperture grill pitch 17 inches measured diagonally 90-degree deflection	Standard image area	Approx. 312 x 234 mm (w/h) (12.3 x 9.3 inches)
Video image area	(15.9" maximum viewing image) Approx. 327 x 241 mm (w/h) (12.9 x 9.5 inches)	Deflection frequency	Horizontal: 31 to 70 KHz Vertical: 50 to 120 Hz
Logical resolution	Horizontal: Max. 1280 dots Vertical: Max. 1024 lines	AC input voltage / current	100 to 120 V, 50-60Hz, 1.8A (max.) 220 to 240 V, 50-60 Hz, 1.0 A
Physical resolution	Horizontal: Max. 1024 dots Vertical: Max. 768 lines	Dimensions	406 x 431.5 x 420 mm (w/h/d) (16 x 17 x 16.5 inches)
		Mass	Approx. 19.0 kg (41 lb. 13 oz.)

Design and specifications are subject to change without notice.

TRINITRON® COLOR COMPUTER DISPLAY

SONY®



POWER SAVING FUNCTION

This monitor meets the power saving guidelines set by the EPA Energy Star Program as well as the more stringent TC092 guidelines (NUTEK). It is capable of reduced power consumption when used with a computer equipped with Display Power Management Signaling (DPMS). By sensing the absence of the sync signal coming from the computer, it will reduce the power consumption as follows:

CAUTION: The Power Saving function will automatically put the monitor into Active-off state if the power switch is turned on without any video signal input. Once the horizontal and vertical syncs are sensed, the monitor will automatically return to its Normal operation state.

	State	Power consumption	Required resumption time	⏻ Power indicator
1	Normal Operation	≤110 W	————	green on
2	Suspend (1st step of power saving)	≤15 W	approx. 3 sec.	orange and green flashes alternately
3	Active-off (2nd step of power saving)	≤15 W	approx. 10 sec.	orange and green flashes alternately
4	Active-off (3rd step of power saving)	≤8 W	approx. 10 sec.	orange on
5	Power - Off	0 W	————	off


TIMING SPECIFICATION

Mode	1	2	3	4	5	6	7	8
Resolution(H x V)	640 x 480	640 x 480	800 x 600	800 x 600	832 x 624	1024 x 768	1280 x 1024	1024 x 768
Dot Clock(MHz)	25.175	36.000	49.500	56.250	57.283	78.750	108.000	94.500
Horizontal								
Hor. Freq. (kHz)	31.469	43.269	46.875	53.674	49.725	60.023	63.981	68.677
H-Total	31.778	23.111	21.333	18.631	20.111	16.660	15.630	14.561
H-Blanking	6.356	5.333	5.172	4.409	5.586	3.657	3.778	3.725
H-Front Porch	0.636	1.556	0.323	0.569	0.559	0.203	0.444	0.508
H-Sync.	3.813	1.556	1.616	1.138	1.117	1.219	1.037	1.016
H-Back Porch	1.907	2.222	3.232	2.702	3.910	2.235	2.296	2.201
H-Active (μsec)	25.422	17.778	16.162	14.222	14.524	13.003	11.852	10.836
Vertical								
Ver. Freq. (Hz)	59.940	85.008	75.000	85.061	74.550	75.029	60.020	84.997
V-Total	525	509	625	631	667	800	1066	808
V-Blanking	45	29	25	31	43	32	42	40
V-Front Porch	10	1	1	1	1	1	1	1
V-Sync.	2	3	3	3	3	3	3	3
V-Back Porch	33	25	21	27	39	28	38	36
V-Active (lines)	480	480	600	600	624	768	1024	768
Sync.								
INT(G)	NO	NO	NO	NO	NO	NO	NO	NO
EXT (H/V)/POLARITY	YES -/	YES -/	YES +/+	YES +/+	YES -/	YES +/+	YES +/+	YES +/+
EXT (CS)/POLARITY	NO	NO	NO	NO	NO	NO	NO	NO
INT/NON INT	NON INT	NON INT	NON INT	NON INT	NON INT	NON INT	NON INT	NON INT

SAFETY CHECK-OUT (US Model only)

After correcting the original service problem, perform the following safety checks before releasing the set to the customer:

1. Check the area of your repair for unsoldered or poorly-soldered connections. Check the entire board surface for solder splashes and bridges.
2. Check the interboard wiring to ensure that no wires are "pinched" or contact high-wattage resistors.
3. Check that all control knobs, shields, covers, ground straps, and mounting hardware have been replaced. Be absolutely certain that you have replaced all the insulators.
4. Look for unauthorized replacement parts, particularly transistors, that were installed during a previous repair. Point them out to the customer and recommend their replacement.
5. Look for parts which, though functioning, show obvious signs of deterioration. Point them out to the customer and recommend their replacement.
6. Check the line cords for cracks and abrasion. Recommend the replacement of any such line cord to the customer.
7. Check the B+ and HV to see if they are specified values. Make sure your instruments are accurate; be suspicious of your HV meter if sets always have low HV.
8. Check the antenna terminals, metal trim, "metallized" knobs, screws, and all other exposed metal parts for AC Leakage. Check leakage as described below.



LEAKAGE TEST

The AC leakage from any exposed metal part to earth ground and from all exposed metal parts to any exposed metal part having a return to chassis, must not exceed 0.5 mA (500 microampere). Leakage current can be measured by any one of three methods.

1. A commercial leakage tester, such as the Simpson 229 or RCA WT-540A. Follow the manufacturers' instructions to use these instructions.
2. A battery-operated AC milliammeter. The Data Precision 245 digital multimeter is suitable for this job.
3. Measuring the voltage drop across a resistor by means of a VOM or battery-operated AC voltmeter. The "limit" indication is 0.75 V, so analog meters must have an accurate low voltage scale. The Simpson's 250 and Sanwa SH-63Trd are examples of passive VOMs that are suitable. Nearly all battery operated digital multimeters that have a 2V AC range are suitable. (See Fig. A)

WARNING!!

NEVER TURN ON THE POWER IN A CONDITION IN WHICH THE DEGAUSS COIL HAS BEEN REMOVED.

SAFETY-RELATED COMPONENT WARNING!!
COMPONENTS IDENTIFIED BY SHADING AND MARK \triangle ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL FOR SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY. CIRCUIT ADJUSTMENTS THAT ARE CRITICAL FOR SAFE OPERATION ARE IDENTIFIED IN THIS MANUAL. FOLLOW THESE PROCEDURES WHENEVER CRITICAL COMPONENTS ARE REPLACED OR IMPROPER OPERATION IS SUSPECTED.

AVERTISSEMENT!!

NE JAMAIS METTRE SOUS TENSION QUAND LA BOBINE DE DEMAGNETISATION EST ENLEVEE.

ATTENTION AUX COMPOSANTS RELATIFS A LA SECURITE!!

LES COMPOSANTS IDENTIFIES PAR UNE TRAME ET PAR UNE MARQUE \triangle SUR LES SCHEMAS DE PRINCIPE, LES VUES EXPLOSEES ET LES LISTES DE PIECES SONT D'UNE IMPORTANCE CRITIQUE POUR LA SECURITE DU FONCTIONNEMENT. NE LES REMPLACER QUE PAR DES COMPOSANTS SONY DONT LE NUMERO DE PIECE EST INDIQUE DANS LE PRESENT MANUEL OU DANS DES SUPPLEMENTS PUBLIES PAR SONY. LES REGLAGES DE CIRCUIT DONT L'IMPORTANCE EST CRITIQUE POUR LA SECURITE DU FONCTIONNEMENT SONT IDENTIFIES DANS LE PRESENT MANUEL. SUIVRE CES PROCEDURES LORS DE CHAQUE REMPLACEMENT DE COMPOSANTS CRITIQUES, OU LORSQU'UN MAUVAIS FONCTIONNEMENT SUSPECTE.

TABLE OF CONTENTS

<u>Section</u>	<u>Title</u>	<u>Page</u>
1. GENERAL	5
2. DISASSEMBLY		
2-1.	Cabinet Removal	8
2-2.	Service Position	8
2-3.	D Board Removal	8
2-4.	Picture Tube Removal	9
3. SAFETY RELATED ADJUSTMENT	10
4. ADJUSTMENTS	11
5. DIAGRAMS		
5-1.	Block Diagram	15
5-2.	Circuit Boards Location	18
5-3.	Schematic Diagrams and Printed Wiring Boards	18
1.	D Board - Schematic Diagram	19
2.	A Board - Schematic Diagram	23
5-4.	Semiconductors	27
6. EXPLODED VIEWS		
6-1.	Chassis	29
6-2.	Packing Materials	30
7. ELECTRICAL PARTS LIST	31

The operating instructions mentioned here are partial abstracts from the Operating Instruction Manual. The page numbers of the Operating Instruction Manual remain as in the manual.


SECTION 1 GENERAL

Getting Started


Before using this monitor, please make sure that the following items are included in your package: Multiscan 100ES/200ES monitor (1), power cord (1), warranty card (1), "Windows95 Monitor Information Disk" (1), and this operating instruction manual (1).

This monitor will sync with any IBM or compatible system equipped with VGA or greater graphics capability. Although this monitor will sync to other platforms running at horizontal frequencies between 30 and 70 kHz, including Macintosh and Power Macintosh system, a cable adapter is required. Please consult your dealer for advice on which adapter is suitable for your needs.

Step 1: With the computer switched off, attach the video signal cable to the video output.



Step 2: Attach the power cord to the monitor and the other end to a power outlet.



Step 3: Turn on the monitor and computer.

Step 4: If necessary, adjust the user controls according to your personal preference.

The installation of your Multiscan 100ES/200ES is complete. Enjoy your monitor.

- 1) VGA is a trademark of IBM Corporation.
- 2) VESA is a trademark of the non-profit organization, Video Electronics Standard Association.
- 3) Macintosh is a trademark of Apple Computer Inc.
- 4) Windows® is a registered trademark of Microsoft Corporation in the United States and other countries.

Using Your Monitor

Preset and User Modes

The Multiscan 100ES/200ES has factory preset modes for the 8 most popular industry standards for true "plug and play" capability. For less common modes, the Multiscan 100ES/200ES's Digital Multiscan Technology will perform all of the complex adjustments necessary to ensure a high quality picture for any timing between 30 and 70 kHz.

CPD-100ES/100EST and CPD-200ES/200EST

No.	Resolution (dots × lines)	Horizontal Frequency	Vertical Frequency	Graphics Mode
1	640 × 480	31.5 kHz	60 Hz	VGA Graphic ¹⁾
2	640 × 480	43.3 kHz	85 Hz	VESA ²⁾
3	800 × 600	46.9 kHz	75 Hz	VESA ²⁾
4	800 × 600	53.7 kHz	85 Hz	VESA ²⁾
5	832 × 624	49.7 kHz	75 Hz	Macintosh 16" Color ²⁾
6	1024 × 768	60.0 kHz	75 Hz	VESA ²⁾
7	1024 × 768	68.7 kHz	85 Hz	VESA ²⁾
8	1280 × 1024	64.0 kHz	60 Hz	VESA ²⁾

For the customers using the Windows®95

Install the new model information of the Sony computer display from "Windows95 Monitor Information Disk" into your PC. (To install the file, refer to the attached "About the Windows95 Monitor Information Disk/File".)

This monitor complies with "VESA DDC", the standards of Plug&Play. If your PC/graphic board complies with DDC, select "Plug and Play Monitor (VESA DDC)" or this monitor's model name (CPD-100ES/100EST or CPD-200ES/200EST) as "Monitor type" from "Control Panel" on Windows95. Some PC/graphic boards do not comply with DDC. Even if they comply with DDC, they may have some problems on connecting to this monitor. In this case, select this monitor's model name (CPD-100ES/100EST or CPD-200ES/200EST) as "Monitor type" on Windows95.

Recommended horizontal timing conditions

Horizontal sync width should be: >1.0 μsec.

Horizontal blanking width should be: >3.6 μsec. (Multiscan 100ES/200ES)
>3.0 μsec. (Multiscan 200ES).

Vertical sync width should be: < 560 μsec.


Note

CPD-100ES/100EST and CPD-200ES/200EST does not apply to Macintosh 21" color mode.

Adjustments

When one of the preset-type signals is input, no picture adjustment is necessary. You can, however, adjust the picture to your preferences by following the procedure described below. You can adjust all items on the OSD (On Screen Display).


Control Panel



Adjusting the Picture Contrast

The adjustment data becomes the common setting for all input signals.

- 1 Press the **◀/▶** button. The "BRIGHTNESS/CONTRAST" OSD appears.



- 2 Press the **◀/▶** buttons to adjust picture contrast.
 - ▶ ... for more contrast
 - ◀ ... for less contrast


The "BRIGHTNESS/CONTRAST" OSD disappears 3 seconds after you release the buttons.

To reset, press the RESET button while the OSD is on.

Adjusting the Picture Brightness

The adjustment data becomes the common setting for all input signals.

- 1 Press the **☀/☿** button. The "BRIGHTNESS/CONTRAST" OSD appears.



- 2 Press the **☀/☿** buttons to adjust picture brightness.
 - ☿ ... for less brightness
 - ☀ ... for more brightness

The "BRIGHTNESS/CONTRAST" OSD disappears 3 seconds after you release the buttons.


To reset, press the RESET button while the OSD is on.

- Before adjusting the items, turn on the unit and feed the video signal from the connected computer/work station.
- Adjustments will be stored automatically.


Adjusting the Picture Centering

The adjustment data becomes the individual setting for each input signal received.


- 1 Press the **CENTER** button. The "CENTER" OSD appears.



- 2 For vertical adjustment Press the **↑/↓** buttons.



For horizontal adjustment Press the **◀/▶** buttons.



To erase the "CENTER" OSD, press the CENTER button again. The "CENTER" OSD automatically disappears 10 seconds after you release the buttons.

To reset, press the RESET button while the OSD is on.


* The horizontal and vertical frequencies for each input signal received appear on the "BRIGHTNESS/CONTRAST" OSD.

Adjustments


Adjusting the Picture Size

The adjustment data becomes the individual setting for each input signal received.

- 1 Press the SIZE button.
The "SIZE" OSD appears.




- 2 For vertical adjustment
Press the buttons.



↑ ... to enlarge
↓ ... to diminish

- For horizontal adjustment
Press the buttons.



← ... to diminish
→ ... to enlarge


To erase the "SIZE" OSD, press the SIZE button again.
The "SIZE" OSD automatically disappears 10 seconds after you release the buttons.

To reset, press the RESET button while the OSD is on.


Adjusting the Picture Rotation

The adjustment data becomes the common setting for all input signals.

- 1 Press the GEOM button.
The "GEOMETRY" OSD appears.



- 2 Press the buttons.
↑ ... to rotate clockwise
↓ ... to rotate counterclockwise




To erase the "GEOMETRY" OSD, press the GEOM button again.
The "GEOMETRY" OSD automatically disappears 10 seconds after you release the buttons.

To reset, press the RESET button while the OSD is on.


Adjusting the Pincushion

The adjustment data becomes the individual setting for each input signal received.


- 1 Press the GEOM button.
The "GEOMETRY" OSD appears.




- 2 Press the buttons.



← ... to diminish the picture sides



→ ... to expand the picture sides




To erase the "GEOMETRY" OSD, press the GEOM button again.
The "GEOMETRY" OSD automatically disappears 10 seconds after you release the buttons.

To reset, press the RESET button while the OSD is on.

Setting the Color Temperature


The selected color temperature becomes the common setting for all input signals.

- 1 Press the COLOR button.
The "COLOR TEMPERATURE" OSD appears.




- 2 Adjust with the and buttons.

To select 5000K or 9300K
Press the buttons.
The selected color temperature is indicated in yellow.



← ... to select 5000K
→ ... to select 9300K

To obtain the desired color temperature between 5000K and 9300K
Press the buttons.



↑ ... for higher temperature
↓ ... for lower temperature

Your most recent adjusted color temperature will be recalled by pressing the button.

To erase the "COLOR TEMPERATURE" OSD, press the COLOR button again.
The "COLOR TEMPERATURE" OSD automatically disappears 10 seconds after you release the buttons.

To reset, press the RESET button while the OSD is on.

Resetting the Adjustment Data to Factory-preset Levels

To reset an adjustment item

Press the button of the adjustment item you want to reset, and then press the RESET button before the OSD (On Screen Display) disappears.

To reset all adjustment data at once (for the received signal)

Press the RESET button when no OSD is shown.



To reset all adjustment data to factory-preset levels

Press and hold the RESET button for more than 2 seconds. All adjustment data are reset to factory-preset levels.



Entering New Timings

When using a video mode that is not one of the factory preset modes, some fine tuning may be required to optimize the display to your preferences. Simply adjust the monitor according to the preceding adjustment instructions. The adjustments will be stored automatically and recalled whenever that mode is used.

A total of 8 user-defined modes can be stored in memory. If the 9th mode is entered, it will replace the first.

Power Saving Function

This monitor meets the power saving guidelines set by the International ENERGY STAR Program as well as the more stringent TCO92 803299 (NUTEK) guidelines. It is capable of reduced power consumption when used with a computer equipped with Display Power Management Signaling (DPMS). By sensing the absence of the sync signal coming from the computer, it will reduce the power consumption as follows:

CAUTION: The Power Saving function will automatically put the monitor into Active-off state if the power switch is turned on without any video signal input. Once the horizontal and vertical syncs are sensed, the monitor will automatically return to its Normal operation state.

	State	Power consumption	Required resumption time	POWER indicator
1	Normal operation	≤ 110 W	—	green on
2	Stand-by (1st step of power saving)	≤ 15 W	approx. 3 sec.	Orange and green flashes alternately
3	Suspend (2nd step of power saving)	≤ 15 W	approx. 3 sec.	Orange and green flashes alternately
4	Active-off (3rd step of power saving)	≤ 8 W	approx. 10 sec.	Orange on
5	Power-off	0 W	—	off

Plug and Play


This monitor complies with DDC™1 and DDC2B, which are the Display Data Channel (DDC) standards of VESA. When a DDC1 host system is connected, the monitor synchronizes with the V. CLK in accordance with the VESA standards and outputs the EDID (Extended Display Identification Data) to the data line.

When a DDC2B host system is connected, the monitor automatically switches to the DDC2B communication.

DDC™ is a trademark of the Video Electronics Standard Association.


Use of the Tilt-Swivel

With the tilt-swivel, this unit can be adjusted to be viewed at your desired angle within 180° horizontally and 20° vertically. To turn the unit vertically and horizontally, hold it at its bottom with both hands.



Damper Wire

Using a white background, very thin horizontal stripes on the screen are visible as shown on the illustration. These stripes are damper wires. These wires are attached to the aperture grille inside the Trinitron tube and are there to dampen vibrations of the aperture grille in order to prevent them from influencing the picture quality.



Troubleshooting

This section may help you isolate a problem and as a result, eliminate the need to contact technical support, allowing continued productivity.

No picture

- ➔ If the POWER indicator is not lit.
 - Check that the power cord is properly connected.
 - Check that the POWER switch is in the "ON" position.
- ➔ If the POWER indicator is flashing in green and orange alternately.
 - Check that your computer power switch is in the "ON" position.
 - The monitor will recover when you press any key on the keyboard of the computer.
 - Check that the video cable is properly connected.
 - Ensure that no pins are bent or pushed in the HD15 connector of the cable.
 - Check that the video card is seated completely in a proper bus slot.
 - Check that the video sync signal is within that specified for the monitor.
 - If using a Macintosh system, check that a proper HD15 - D15 adapter is provided to work correctly with your Macintosh.
 - The monitor has a self-diagnose function. After disconnecting the video signal cable from the computer, turn on the POWER switch of the monitor. Press and hold the "+" side of the button for 2 seconds, then color bars will appear. The monitor is operating normally if the red, green, and blue color bars appear. Contact the maker of the computer to which the monitor is connected.
- ➔ If the POWER indicator is flashing.
 - There is a potential monitor failure. Contact your dealer.

If the message of "OUT OF SCAN RANGE" appears on the screen

- ➔ Check that the video sync signal is specified for the monitor.

Picture is scrambled

- ➔ Check your graphics board manual for the proper monitor setting on your Multiscan 100ES/200ES.
- ➔ Check this manual and confirm that the graphic mode and the frequency at which you are trying to operate is supported. Even within the proper range some video boards may have a sync pulse that is too narrow for the monitor to sync correctly.

Color is not uniform

- ➔ If the monitor is close to any potential sources of magnetic fields such as a speaker, or you turn the monitor while the POWER switch is in the "ON" position, color may not be uniform. Trip the POWER switch once to activate the Auto-degauss cycle*.

Picture is flickering

- ➔ If the refresh rate is not appropriate, the picture may flicker. Set the refresh rate of the non-interlace mode as high as possible on the computer. For details on how to set the refresh rate, consult the dealer of your computer or video board.

Screen image is not centered or sized properly

- ➔ Adjust the "CENTER," "SIZE," or "GEOMETRY" on the OSD (pages 5, 6).
- ➔ Some video modes do not fill the screen to the edge of the monitor. There is no single answer to solve the problem. There is a tendency to have this problem on higher refresh timings and Macintosh video timings.

Picture is fuzzy

- ➔ Adjust the "CONTRAST" and "BRIGHTNESS" on the OSD (page 5). We have come across several brands of SVGA boards that have an excessive video output level which creates a fuzzy picture at max contrast.
- ➔ Trip the POWER switch once to activate the Auto-degauss cycle*.

Picture bounces or has wavy oscillations

- ➔ Isolate and eliminate any potential sources of electric or magnetic fields. Common causes for this symptom are electric fans, fluorescent lighting, laser printers, and so on.
- ➔ If you have another monitor close to this monitor, increase the distance between them to reduce the interference.
- ➔ Try plugging the monitor into a different AC outlet, preferably on a different circuit.
- ➔ Try the monitor on a completely different computer in a different room.

Picture appears to be ghosting

- ➔ Eliminate the use of video cable extension cables and/or video switch boxes if this symptom occurs. Excessive cable length or weak connections can produce this symptom.

A fine horizontal line (wire) is visible

- ➔ This wire stabilizes the vertically striped Aperture Grille (page 8). This Aperture Grille allows more light to pass through to the screen giving the Trinitron CRT more color and brightness.

Wavy or elliptical (moire) pattern is visible

- ➔ Due to the relationship between resolution, monitor AG pitch and the pitch of some image patterns, certain screen backgrounds, especially gray, sometimes show moire. This can only be eliminated by changing your desktop pattern.

Just after turning the monitor on, a "boon" noise is heard


- ➔ Just after turning the monitor on, a noise may be heard for about 3 seconds. This noise is not failure, it is caused by the Auto-degauss cycle*.

* The Auto-degauss function demagnetizes the metal frame of the CRT to obtain a neutral field for uniform color reproduction. If a second degauss cycle is needed, allow a minimum interval of 20 minutes for the best result.


- If the problem persists, call your authorized Sony dealer from a location near your monitor.
- Note the model name and the serial number of your monitor. Also note the make and name of your computer and video board.

SECTION 2 DISASSEMBLY


2-1. CABINET REMOVAL




2-2. SERVICE POSITION



2-3. D BOARD REMOVAL




2-4. PICTURE TUBE




• REMOVAL OF THE ANODE-CAP

NOTE: Short circuit the anode of the picture tube and the anode cap to the metal chassis, CRT shield or carbon painted on the CRT, after removing the anode.


• REMOVAL PROCEDURES



① Turn up one side of the rubber cap in the direction indicated by arrow a).




② Use your thumb to pull the rubber cap firmly in the direction indicated by arrow b).



③ When one side of the rubber cap separates from the anode button, the anode-cap can be removed by turning the rubber cap and pulling it in the direction of arrow c).

• HOW TO HANDLE AN ANODE-CAP

- ① Do not use sharp objects which may cause damage to the surface of the anode-cap.
- ② Do not squeeze the rubber covering too hard to avoid damaging the anode-cap. A material fitting called a shatter-hook terminal is built into the rubber.
- ③ Do not force turn the foot of the rubber cover. This may cause the shatter-hook terminal to protrude and damage the rubber.



SECTION 3 SAFETY RELATED ADJUSTMENT


- When replacing parts shown in the table below, the following operational checks must be performed as a safety precaution against X-rays emissions from the unit.

D - BOARD
Part Replaced (☒)
RV501
Part Replaced (☑)
IC801, IC901, IC904, FBT T501, D511, D515, D596, R532, R533, R534, R535, R538, R539, R540, R541, R542, R543, R544, R545, R807, R822, R823, R824, R939, R996, RV501, C509, C515, C516, C517, C519, C531, C542, C548, C549, C802, C814, C815, C904, C910, R598, R599

※ Allow the unit to warm up for one minute prior to checking the following conditions:

a) HV Regulator Check

- 1) Input white cross hatch signal. (fH = 64 kHz)
- 2) Set H.Size data to minimum.
- 3) Cut off Screen VR (G2).
- 4) Input voltage: 120 ± 2 VAC
- 5) Confirm that the voltage is within the voltage range shown below:
Standard voltage: $25.0KV \pm 0.2KV$
- 6) When replacing components identified by ☑, make sure to recheck the High Voltage.
- 7) Verify the High Voltage as shown above ($25.0KV \pm 0.2KV$) is within specification. If not, set H. SIZE data at minimum (-127) and then adjust RV501 on "D" Board.
- 8) After adjusting the High Voltage within specification, put the RV cover on RV501 as shown below and apply sufficient amount of RTV around RV501.



b) HV Hold-Down Check

- 1) Using an external DC Power supply, apply the voltage shown below between cathode of D511 on "D" Board and GND, and confirm that the HV Hold-Down circuit works. (Raster disappears)
Standard voltage: $35.00 + 0.00$ VDC
- 0.10

Check Condition

- Input voltage : 120 ± 2 VAC
- Input signal : Any pattern (fH = 64 kHz)
- Controls : CONT → Maximum
: BRT → Center

c) Beam Protector Check

- 1) Using an external DC power supply, apply the voltage $7.00 + 0.05$ VDC between pin ⑪ of FBT (T501) and GND, and confirm that the voltage of both ends C519 is within the voltage range shown below.
Standard voltage: Less than 3.26 VDC

Check Condition


- Input voltage : 120 ± 2 VAC
- Input signal : Any pattern (fH = 64 kHz)
- Controls : CONT → Maximum
: BRT → Center

d) +B MAX. Check

- 1) Input white cross hatch (fH = 64 kHz) signal.
- 2) Set CONT and BRT to Maximum
- 3) Input voltage: 120 ± 2 VAC
Note: Use NF power supply or make sure that distortion factor is 3% or less.
- 4) Confirm that the voltage is within the voltage range shown below.
Standard voltage: 151.0 ± 4.25 VDC
Measurement Point: CN505 Pin 1 and GND

SECTION 4 ADJUSTMENTS

Connect the communication cable of the connector located on the D board on the monitor. Run the service software and then follow the instructions.



*The parts above (1)~(3) are necessary for DAS adjustment.

※ Allow a 30 minute warm-up period prior to making the following adjustments.

● Landing Rough Adjustment

1. Enter the full white signal.
2. Adjust the contrast to the maximum.
3. Make the screen monogreen.
4. Reverse the DY, and adjust coarsely the purity magnet so that a green raster positions in the center of screen.
5. Moving the DY forward, adjust so that an entire screen becomes monogreen.
6. Adjust the tilt of DY, and fix lightly with a clamp.

● Landing Fine Adjustment

1. Place the set in the Helmholtz coil.
2. Enter a green signal only.
3. Degauss the entire screen with hand-degausser. Then auto degauss it.
4. Attach a wobbling coil to the specified position of CRT neck.
5. Attach a landing adjuster sensor on the CRT.
6. Using a landing checker, adjust the DY position, purity on DY, tilt of DY.
7. Clamp the DY screw.

Clamping torque: 22 ± 2 kgcm (2.2 ± 0.2 Nm)



● Convergence Rough Adjustment

1. Enter the white crosshatch signal.
2. Adjust roughly the horizontal and vertical convergence at four-pole magnet.
3. Adjust roughly HMC and VMC at six-pole magnet.

● Convergence Fine Adjustment


Set DY four-pole magnet to mechanical center before adjustment.

This should be prime mode.




1. Receive R.B. crosshatch.
2. Adjust H. STAT and V. STAT at four-pole magnet.

< 4 Pole Magnet >



3. Receive White cross-hatch.
4. Adjust HMC and VMC at six-pole magnet.


< 6 Pole Magnet >



5. Display R and B cross hatch patterns.
6. Adjust H STAT and V STAT with 4-pole magnet.
7. Display white cross hatch patterns.
8. Adjust HMC and VMC with 6-pole magnet.
9. Display R and B cross hatch patterns.
10. Adjust XCV and XCV roller.
11. Adjust XBV and XBV reactor.
12. Adjust V.STAT with 4-pole magnet.

Repeat steps 7 to 12 above and make R, G, B of both vertical and horizontal lines to be overlaid at the center of the x-axis.

13. Adjust H.TILT with TLH Corrector.
14. Adjust XCV with XCV core.




15. Adjust V.TILT with TLV VR.

16. Adjust Y.CROSS with YCH VR.




17. Adjust YBH with YBH VR.





18. Paint lock the four-pole magnet ,six-pole magnet, XBV reactor, XCV corrector and TLH corrector handle.


<VR Adjustment on DY>




Zero Position NECK Assembly



● Vertical and Horizontal Position and Size Specification




● Convergence Specification




● Focus Adjustment

Adjust focus (V) and focus (H) for optimum focus.



5-2. CIRCUIT BOARDS LOCATION



5-3. SCHEMATIC DIAGRAMS AND PRINTED WIRING BOARDS

Note:

- All capacitors are in μF unless otherwise noted. pF: $\mu\mu\text{F}$
- 50 WV or less are not indicated except for electrolytic.
- Indication of resistance, which does not have one for rating electrical power, is as follows.

Pitch: 5 mm
Rating electrical power 1/4 W (CHIP: 1/10 W)

- All resistors are in ohms.
- : nonflammable resistor.
- : fusible resistor.
- Δ : internal component.
- : panel designation and adjustment for repair.
- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
- \perp : earth-ground.
- : earth-chassis.
- The components identified by in this basic schematic diagram have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.
- When replacing components identified by , make the necessary adjustments by using RV501 () as indicated. (See page 10)

Note: The components identified by shading and mark Δ are critical for safety. Replace only with part number specified.


Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

- When replacing parts shown in the table below, be sure to perform the safety related adjustment.

D - BOARD
Part Replaced ()
RV501
Part Replaced ()
IC801, IC901, IC904, FBT T501, D511, D515, D596, R532, R533, R534, R535, R538, R539, R540, R541, R542, R543, R544, R545, R807, R822, R823, R824, R939, R996, RV501, C509, C515, C516, C517, C519, C542, C548, C549, C802, C814, C815, C904, C910, R598, R599, C531

- All voltages are in Volts.
- Readings are taken with a 10 M Ω digital multimeter
- Readings are taken with a color-bar signal input.
- Voltage variations may be noted due to normal production tolerances.
- * : Can not be measured.
- Circled numbers are waveform references.
- : B +bus.
- : B - bus.

A VIDEO



1 1.2KV
CONNECT TO BOARD CN50

CN09
TO BRKT CABLE

CN02
TO BRKT CABLE

CN03
TO BRKT CABLE









































CN05
CN05

1	GND
2	GND
3	+12V
4	+12
5	+5V
6	+12
7	+5V
8	+12
9	+12
10	GND
11	+80V
12	NC
13	+150V

CONNECT TO BOARD CN08

CN04

5-4. SEMICONDUCTORS



SECTION 6 EXPLODED VIEWS

- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The component parts of an assembly are indicated by the reference numbers in the remarks column.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

Note:


The components identified by shading and mark Δ are critical for safety. Replace only with part number specified.

Note:

Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.


6-1. CHASSIS

- 7-685-648-79 SCREW +BVTP 3x12
- △ 7-685-663-71 SCREW +BVTP 4x16
- ▼ 7-685-882-09 SCREW +BVTT 4x10
- 7-685-646-79 SCREW +BVTP 3x8



REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
1	*	X-4034-876-1	BEZEL ASSY	2-3	21	7-685-659-71	SCREW + BVTT 4x8 (S)
2		4-060-596-01	SPRING, COMPRESSION	22	*	4-060-151-01	STOPPER, CABLE
3		4-060-598-01	BUTTON, POWER	23		1-775-535-11	CABLE ASSY VIDEO (15P D-SUB)
4	*	4-060-152-01	LABEL, ENERGY STAR	24	*	4-060-150-01	BRACKET, CABLE
5	Δ	8-738-728-82	ITC ASSY (17FRFM-RS3) (CPD-200ES SH)	25	*	4-060-612-01	COVER, BOTTOM
5	Δ	8-738-733-82	ITC ASSY (17FRFM-R2) (CPD-200ES EQ)	26	*	4-060-178-01	HOLDER, STAND
6	Δ	8-738-728-05	CRT, 17FRFM (CPD-200ES SH)	27		4-060-183-01	STOPPER (A)
6	Δ	8-738-733-05	CRT, 17FRFM (CPD-200ES EQ)	28	*	4-060-613-01	SLIDER
7		4-060-166-01	SPACER, DY	29	*	4-060-180-01	RING, TILT SWIVEL
8	Δ	1-452-923-21	NECK ASSY (NA-2914)	30	*	X-4034-879-1	STAND BASE, ASSY
9	Δ	8-451-487-11	DY Y17FRG-M	31		X-4034-877-1	CABINET ASSY
10		1-500-386-11	FILTER CLAMP (FERRITE CORE)	32	*	4-060-602-11	LABEL, INFORMATION (CPD-200ES SH)
11	*	A-1298-231-A	A BOARD, COMPLETE	32	*	4-060-602-01	LABEL, INFORMATION (CPD-200ES EQ)
13		4-060-603-01	SPRING, TENSION	33		4-060-155-01	HOLDER, HV CABLE
14	Δ	1-416-282-21	COIL, DEMAGNETIZATION	34		1-452-032-00	MAGNET, DISC
15	*	4-060-606-01	SPACER, DGC	35	*	X-4034-792-1	PERMALLOY ASSY, STAND
16		4-365-808-01	SCREW (5), TAPPING				
17	*	A-1346-658-A	D BOARD, COMPLETE				
18	Δ	1-453-240-21	TRANSFORMER ASSY, FLYBACK(NX-4103//JIE4)				
19		1-543-653-11	CORE ASSY,BEAD (DIVISION TYPE)				
20		4-389-025-01	SCREW (M4x8)(EXT.TOOTHWASHER)				

6-2. PACKING MATERIALS



<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>	<u>REMARK</u>
51	3-860-654-01	MANUAL, INSTRUCTION	
52 *	4-060-618-01	CUSHION, RIGHT	
53 Δ	1-558-481-11	CORD SET, POWER (CPD-200ES SH)	
53 Δ	1-765-719-11	CORD SET, POWER (CPD-200ES EQ)	
54 *	4-060-620-01	BAG, POLYETHYLENE	
55 *	4-060-617-01	CUSHION, LEFT	
56 *	4-060-621-01	INDIVIDUAL CARTON (CPD-200ES SH)	
56 *	4-061-139-01	INDIVIDUAL CARTON (CPD-200ES EQ)	



Note: The components identified by shading and mark Δ are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK
C307	1-164-346-11	CERAMIC CHIP 1MF	16V
C309	1-163-259-91	CERAMIC CHIP 220PF	5% 50V
C330	1-107-905-11	ELECT 4.7MF	20% 50V
C334	1-164-004-11	CERAMIC CHIP 0.1MF	10% 25V
C351	1-137-528-11	FILM 0.1MF	10% 250V
CONNECTOR			
CN301	1-506-108-41	PIN, CONNECTOR (TERMINAL PIN)	
CN302	1-695-915-11	TAB (CONTACT)	
CN303	1-695-915-11	TAB (CONTACT)	
CN305	1-564-513-11	PLUG, CONNECTOR 10P	
CN306 *	1-564-510-11	PLUG, CONNECTOR 7P	
CN307 *	1-564-512-11	PLUG, CONNECTOR 9P	
CN309	1-564-511-11	PLUG, CONNECTOR 8P	
CN310 *	1-564-507-11	PLUG, CONNECTOR 4P	
CN311 *	1-564-507-11	PLUG, CONNECTOR 4P	
CN399	1-695-915-11	TAB (CONTACT)	
DIODE			
D002	8-719-911-19	DIODE 1SS119-25	
D014	8-719-911-19	DIODE 1SS119-25	
D016	8-719-109-89	DIODE RD5.6ESB2	
D017	8-719-109-89	DIODE RD5.6ESB2	
D101	8-719-911-19	DIODE 1SS119-25	
D102	8-719-911-19	DIODE 1SS119-25	
D104	8-719-970-83	DIODE HSS82	
D105	8-719-970-83	DIODE HSS82	
D106	8-719-970-83	DIODE HSS82	
D201	8-719-911-19	DIODE 1SS119-25	
D202	8-719-911-19	DIODE 1SS119-25	
D204	8-719-970-83	DIODE HSS82	
D205	8-719-970-83	DIODE HSS82	
D206	8-719-970-83	DIODE HSS82	
D301	8-719-911-19	DIODE 1SS119-25	
D302	8-719-911-19	DIODE 1SS119-25	
D304	8-719-970-83	DIODE HSS82	
D305	8-719-970-83	DIODE HSS82	
D306	8-719-970-83	DIODE HSS82	
D307	8-719-110-49	DIODE RD18ESB2	
FERRITE BEAD			
FB001	1-412-911-11	INDUCTOR	
FB003	1-412-911-11	INDUCTOR	
FB004	1-412-911-11	INDUCTOR	
FB005	1-412-911-11	INDUCTOR	
FB006	1-412-911-11	INDUCTOR	

REF.NO.	PART NO.	DESCRIPTION	REMARK
FB007	1-412-911-11	INDUCTOR	
FB008	1-412-911-11	INDUCTOR	
FB009	1-412-911-11	INDUCTOR	
FB010	1-412-911-11	INDUCTOR	
FB011	1-412-911-11	INDUCTOR	
FB012	1-412-911-11	INDUCTOR	
FB013	1-412-911-11	INDUCTOR	
FB101 Δ	1-500-104-21	INDUCTOR	
FB102 Δ	1-414-793-21	INDUCTOR	
FB103	1-500-104-21	INDUCTOR	
FB104	1-412-911-11	INDUCTOR	
FB110	1-412-911-11	INDUCTOR	
FB201 Δ	1-500-104-21	INDUCTOR	
FB202 Δ	1-414-793-21	INDUCTOR	
FB203	1-500-104-21	INDUCTOR	
FB210	1-412-911-11	INDUCTOR	
FB301 Δ	1-500-104-21	INDUCTOR	
FB302 Δ	1-414-793-21	INDUCTOR	
FB303	1-500-104-21	INDUCTOR	
FB310	1-412-911-11	INDUCTOR	
IC			
IC001	8-759-474-78	IC MM1382	
IC002	8-759-435-33	IC LM2405T	
IC003	8-759-399-76	IC SNY425	
IC004	8-759-434-40	IC TDA6103Q/N3,112	
IC005	8-759-634-51	IC M5218AP	
JACK			
J001 Δ	1-251-598-11	SOCKET, CRT	
COIL			
L001	1-412-537-31	INDUCTOR	100UH
L101	1-407-500-00	INDUCTOR	4.7MMH
L105	1-410-750-41	INDUCTOR	0.47UH
L201	1-407-500-00	INDUCTOR	4.7MMH
L205	1-410-750-41	INDUCTOR	0.47UH
L301	1-407-500-00	INDUCTOR	4.7MMH
L305	1-410-750-41	INDUCTOR	0.47UH
TRANSISTOR			
Q001	8-729-032-61	TRANSISTOR 2SC5022-02	
Q002	8-729-216-22	TRANSISTOR 2SA1162-G	
Q003	8-729-216-22	TRANSISTOR 2SA1162-G	
Q004	8-729-120-28	TRANSISTOR 2SC1623-L5L6	



Note: The components identified by shading and mark Δ are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifique.

REF.NO. PART NO. DESCRIPTION REMARK

SPARK GAP

SG001	Δ 1-519-422-11	GAP, SPARK	
SG003	Δ 1-517-499-21	GAP, SPARK	
SG101	Δ 1-517-499-21	GAP, SPARK	
SG201	Δ 1-517-499-21	GAP, SPARK	
SG301	Δ 1-517-499-21	GAP, SPARK	

CRYSTAL

X1 1-567-890-11 VIBRATOR, CRYSTAL



* A-1346-658-A D BOARD, COMPLETE

- 1-533-223-11 HOLDER, FUSE
- * 1-900-801-67 CONNECTOR ASSY
- 4-060-502-01 HOLDER, LED (A)
- 4-382-854-11 SCREW (M3X10), P, SW (+)
- 4-389-025-01 SCREW (M4) (EXT TOOTH WASHER)
- 7-685-647-79 SCREW +BVTP 3X10 TYPE2

CAPACITOR

C401	1-128-528-11	ELECT	470MF	20%	25V
C402	1-106-228-00	MYLAR	0.22MF	10%	100V
C403	1-137-399-11	FILM	0.1MF	5%	50V
C404	1-107-894-11	ELECT	220MF	20%	35V
C405	1-101-006-00	CERAMIC	0.047MF		50V
C406	1-137-375-11	FILM	0.068MF	5%	50V
C410	1-107-914-11	ELECT	1000MF	20%	25V
C420	1-137-368-11	FILM	0.0047MF	5%	50V
C500	1-136-169-00	FILM	0.22MF	5%	50V
C502	1-137-370-11	FILM	0.01MF	5%	50V
C503	1-107-667-11	ELECT	2.2MF	20%	160V
C505	1-126-964-11	ELECT	10MF	20%	50V
C506	1-137-370-11	FILM	0.01MF	5%	50V
C507	1-162-318-11	CERAMIC	0.001MF	10%	500V
C508	1-109-843-11	CERAMIC	33PF	5%	2KV
C509	1-137-374-11	FILM	0.047MF	5%	50V
C512	1-137-399-11	FILM	0.1MF	5%	50V
C513	1-106-383-00	MYLAR	0.047MF	10%	200V
C514	1-126-941-11	ELECT	470MF	20%	25V
C515	1-136-203-11	FILM	10000PF	5%	630V
C516	1-126-960-11	ELECT	1MF	20%	50V
C517	1-137-370-11	FILM	0.01MF	5%	50V
C518	1-165-136-11	CERAMIC	3300PF	10%	500V
C519	1-126-961-11	ELECT	2.2MF	20%	50V

REF.NO. PART NO. DESCRIPTION REMARK

C520	1-107-955-11	ELECT	100MF	20%	200V
C521	1-126-960-11	ELECT	1MF	20%	50V
C523	1-106-375-12	MYLAR	0.022MF	10%	100V
C527	1-162-117-00	CERAMIC	100PF	10%	500V
C528	1-126-965-11	ELECT	22MF	20%	50V
C529	1-107-846-11	FILM	0.1MF	5%	400V
C531	1-137-399-11	FILM	0.1MF	5%	50V
C532	1-106-364-11	MYLAR	0.01MF	10%	200V
C533	1-164-735-11	CAPACITOR	0.0015MF	10%	500V
C534	1-115-349-51	CERAMIC	0.01MF		2KV
C536	1-106-375-12	MYLAR	0.022MF	10%	100V
C540	Δ 1-136-064-00	FILM	2200PF	3%	2KV
C541	Δ 1-113-576-11	FILM	0.0043MF	3%	2.5KV
C542	1-137-370-11	FILM	0.01MF	5%	50V
C547	1-126-941-11	ELECT	470MF	20%	25V
C548	1-137-425-11	FILM	0.33MF	10%	100V
C549	1-137-399-11	FILM	0.1MF	5%	50V
C550	1-117-206-21	FILM	0.36MF	5%	250V
C562	1-107-846-11	FILM	0.1MF	5%	400V
C565	1-136-169-00	FILM	0.22MF	5%	50V
C566	1-137-370-11	FILM	0.01MF	5%	50V
C567	1-137-370-11	FILM	0.01MF	5%	50V
C568	1-137-370-11	FILM	0.01MF	5%	50V
C569	1-137-370-11	FILM	0.01MF	5%	50V
C570	1-115-519-11	FILM	0.56MF	5%	250V
C576	1-115-514-11	FILM	0.22MF	5%	250V
C582	1-161-754-00	CERAMIC	0.001MF	10%	2KV
C583	1-106-375-12	MYLAR	0.022MF	10%	100V
C593	1-109-945-11	FILM	0.18MF	5%	200V
C598	1-137-399-11	FILM	0.1MF	5%	50V
C599	1-128-582-11	ELECT	10MF	20%	100V
C601	Δ 1-104-708-11	FILM	0.47MF	20%	250V
C602	Δ 1-107-533-11	FILM	1MF	20%	250V
C603	Δ 1-113-912-11	CERAMIC	0.0047MF	20%	250V
C604	Δ 1-113-912-11	CERAMIC	0.0047MF	20%	250V
C605	Δ 1-113-896-11	CERAMIC	220PF	10%	250V
C606	Δ 1-113-896-11	CERAMIC	220PF	10%	250V
C607	1-137-368-11	FILM	0.0047MF	5%	50V
C608	1-107-894-11	ELECT	220MF	20%	35V
C609	1-137-399-11	FILM	0.1MF	5%	50V
C610	1-102-115-00	CERAMIC	560PF	10%	50V
C611	1-136-177-00	FILM	1MF	5%	50V
C612	1-137-370-11	FILM	0.01MF	5%	50V
C614	1-102-973-00	CERAMIC	100PF	5%	50V
C615	1-137-364-11	FILM	0.001MF	5%	50V
C616	1-113-912-11	CERAMIC	0.0047MF	20%	250V
C617	1-106-343-00	MYLAR	0.001MF	10%	100V
C618	1-107-884-11	ELECT	1000MF	20%	16V



Note: The components identified by shading and mark **Δ** are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un trame et une marque **Δ** sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK			REF.NO.	PART NO.	DESCRIPTION	REMARK		
C619	1-137-366-11	FILM	0.0022MF	5%	50V	C916	1-126-961-11	ELECT	2.2MF	20%	50V
C620	Δ 1-109-984-11	ELECT	390MF	20%	400V	C917	1-126-961-11	ELECT	2.2MF	20%	50V
C621	1-136-203-11	FILM	10000PF	5%	630V	C918	1-126-961-11	ELECT	2.2MF	20%	50V
C622	Δ 1-113-912-11	CERAMIC	0.0047MF	20%	250V	C919	1-126-961-11	ELECT	2.2MF	20%	50V
C628	1-137-399-11	FILM	0.1MF	5%	50V	C920	1-126-961-11	ELECT	2.2MF	20%	50V
C634	1-126-941-11	ELECT	470MF	20%	25V	C921	1-126-961-11	ELECT	2.2MF	20%	50V
C635	1-126-935-11	ELECT	470MF	20%	16V	C923	1-137-370-11	FILM	0.01MF	5%	50V
C650	1-125-700-11	ELECT	220MF	20%	200V	C924	1-137-399-11	FILM	0.1MF	5%	50V
C651	1-107-933-11	ELECT	100MF	20%	100V	C925	1-126-934-11	ELECT	220MF	20%	16V
C652	1-107-914-11	ELECT	1000MF	20%	25V	C926	1-137-364-11	FILM	0.001MF	5%	50V
C653	1-126-941-11	ELECT	470MF	20%	25V	C927	1-104-664-11	ELECT	47MF	20%	25V
C662	1-126-941-11	ELECT	470MF	20%	25V	C928	1-137-370-11	FILM	0.01MF	5%	50V
C675	1-137-364-11	FILM	0.001MF	5%	50V	C929	1-137-399-11	FILM	0.1MF	5%	50V
C678	1-162-115-00	CERAMIC	330PF	10%	2KV	C930	1-126-965-11	ELECT	22MF	20%	50V
C802	1-102-074-00	CERAMIC	0.001MF	10%	50V	C931	1-136-169-00	FILM	0.22MF	5%	50V
C803	1-102-106-00	CERAMIC	100PF	10%	50V	C932	1-137-399-11	FILM	0.1MF	5%	50V
C804	1-137-364-11	FILM	0.001MF	5%	50V	C933	1-126-934-11	ELECT	220MF	20%	16V
C805	1-126-965-11	ELECT	22MF	20%	50V	C934	1-126-961-11	ELECT	2.2MF	20%	50V
C806	1-126-767-11	ELECT	1000MF	20%	16V	C935	1-136-169-00	FILM	0.22MF	5%	50V
C807	1-137-399-11	FILM	0.1MF	5%	50V	C937	1-126-935-11	ELECT	470MF	20%	16V
C808	1-137-365-11	FILM	0.0015MF	5%	50V	C939	1-137-374-11	FILM	0.047MF	5%	50V
C810	1-124-768-11	ELECT	4.7MF	20%	35V	C940	1-137-374-11	FILM	0.047MF	5%	50V
C811	1-137-399-11	FILM	0.1MF	5%	50V	C941	1-136-169-00	FILM	0.22MF	5%	50V
C812	1-137-365-11	FILM	0.0015MF	5%	50V	C942	1-126-926-11	ELECT	1000MF	20%	10V
C813	1-137-370-11	FILM	0.01MF	5%	50V	C943	1-137-372-11	FILM	0.022MF	5%	50V
C814	1-136-169-00	FILM	0.22MF	5%	50V	C944	1-137-366-11	FILM	0.0022MF	5%	50V
C815	1-137-366-11	FILM	0.0022MF	5%	50V	C945	1-137-372-11	FILM	0.022MF	5%	50V
C817	1-126-933-11	ELECT	100MF	20%	16V	C946	1-102-106-00	CERAMIC	100PF	10%	50V
C818	1-137-399-11	FILM	0.1MF	5%	50V	C948	1-137-399-11	FILM	0.1MF	5%	50V
C819	1-136-173-00	FILM	0.47MF	5%	50V	C950	1-117-378-11	FILM	1MF	5%	50V
C820	1-137-366-11	FILM	0.0022MF	5%	50V	C955	1-102-106-00	CERAMIC	100PF	10%	50V
C821	1-102-112-00	CERAMIC	330PF	10%	50V	C960	1-136-177-00	FILM	1MF	5%	50V
C822	1-137-368-11	FILM	0.0047MF	5%	50V	C961	1-137-399-11	FILM	0.1MF	5%	50V
C901	1-137-399-11	FILM	0.1MF	5%	50V	C962	1-137-399-11	FILM	0.1MF	5%	50V
C902	1-137-368-11	FILM	0.0047MF	5%	50V	C963	1-137-399-11	FILM	0.1MF	5%	50V
C903	1-102-951-00	CERAMIC	15PF	5%	50V	C967	1-102-106-00	CERAMIC	100PF	10%	50V
C904	1-137-399-11	FILM	0.1MF	5%	50V	C968	1-126-960-11	ELECT	1MF	20%	50V
C905	1-137-399-11	FILM	0.1MF	5%	50V	C969	1-137-364-11	FILM	0.001MF	5%	50V
C906	1-136-173-00	FILM	0.47MF	5%	50V	C970	1-102-106-00	CERAMIC	100PF	10%	50V
C907	1-126-963-11	ELECT	4.7MF	20%	50V	C1801	1-102-112-00	CERAMIC	330PF	10%	50V
C908	1-102-951-00	CERAMIC	15PF	5%	50V	C1802	1-102-112-00	CERAMIC	330PF	10%	50V
C910	1-104-664-11	ELECT	47MF	20%	25V	C1803	1-136-169-00	FILM	0.22MF	5%	50V
C911	1-126-768-11	ELECT	2200MF	20%	16V						
C912	1-126-961-11	ELECT	2.2MF	20%	50V						
C913	1-126-961-11	ELECT	2.2MF	20%	50V						
C915	1-124-768-11	ELECT	4.7MF	20%	35V						

CONNECTOR

CN501 * 1-580-798-11 CONNECTOR PIN (DY) 6P



Note: The components identified by shading and mark **Δ** are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un trame et une marque **Δ** sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK
FB612	Δ 1-412-911-11	INDUCTOR	
FB613	Δ 1-412-911-11	INDUCTOR	
FB614	Δ 1-412-911-11	INDUCTOR	
FB615	Δ 1-412-911-11	INDUCTOR	
FB901	1-412-911-11	INDUCTOR	
FB902	1-412-911-11	INDUCTOR	
FB903	1-412-911-11	INDUCTOR	
FB904	1-412-911-11	INDUCTOR	
FB905	1-412-911-11	INDUCTOR	
TERMINAL			
GT001 *	1-537-738-21	TERMINAL, EARTH	
GT002 *	1-537-738-21	TERMINAL, EARTH	
IC			
IC400	8-759-803-42	IC LA6500-FA	
IC401	8-759-980-58	IC TDA8172	
IC601	Δ 8-759-399-81	IC MC44603P	
IC603	Δ 8-749-014-41	IC MOC8105TV	
IC604	Δ 8-759-072-98	IC TDA8138A	
IC652	Δ 8-759-466-13	IC TL431ACLPRP	
IC801	Δ 8-759-466-15	IC UPC6753	
IC901	8-749-014-36	IC ST7272N5B1/CUS	
IC902	Δ 8-759-269-04	IC SN74HCT02AN	
IC903	8-759-165-81	IC PST600D-T	
IC904	Δ 8-759-399-77	IC TDA9105	
COIL			
L501	1-412-550-11	INDUCTOR	1.2MMH
L504	1-459-104-00	COIL, WITH CORE	
L505	1-412-531-31	INDUCTOR	33UH
L506	1-459-104-00	COIL, WITH CORE	
L507	1-412-531-31	INDUCTOR	33UH
L513	1-409-896-11	COIL, HORIZONTAL LINEARITY	
L650	1-412-537-31	INDUCTOR	100UH
L651	1-412-537-31	INDUCTOR	100UH
L652	1-406-665-11	COIL, CHOKE	100UH
L653	1-412-537-31	INDUCTOR	100UH
L801	1-410-645-31	INDUCTOR	100UH
L900	1-410-645-31	INDUCTOR	100UH
FILTER			
LF601	Δ 1-429-180-11	TRANSFORMER, LINE FILTER	

REF.NO.	PART NO.	DESCRIPTION	REMARK
TRANSISTOR			
Q500	8-729-031-89	TRANSISTOR 2SC3941A-Q(TA)	
Q501	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q502	Δ 8-729-043-37	TRANSISTOR IRFU214	
Q503	8-729-027-97	TRANSISTOR IRFI9630G-LF	
Q504	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q505	8-729-119-76	TRANSISTOR 2SA1175-HFE	
Q507	8-729-030-67	TRANSISTOR 2SC5129(LBSONY1)	
Q508	Δ 8-729-042-24	TRANSISTOR 2SB949-LE	
Q509	Δ 8-729-042-33	TRANSISTOR 2SD1275Q-LE	
Q510	8-729-027-82	TRANSISTOR IRFPE40LF20	
	4-060-503-01	SHEET, INSULATING (for Q510)	
Q512	8-729-027-14	TRANSISTOR 2SK1904	
Q513	8-729-027-14	TRANSISTOR 2SK1904	
Q514	8-729-027-14	TRANSISTOR 2SK1904	
Q515	8-729-140-50	TRANSISTOR 2SC3209LK	
Q528	8-729-140-50	TRANSISTOR 2SC3209LK	
Q529	8-729-028-34	TRANSISTOR 2SD1640Q.R	
Q602	Δ 8-729-926-79	TRANSISTOR IRFIBC40	
Q654	8-729-141-83	TRANSISTOR 2SB1094-LK	
Q655	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q656	Δ 8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q670	8-729-011-92	TRANSISTOR 2SC2001TP-K1K2	
Q901	8-729-119-78	TRANSISTOR 2SC2785-HFE	
Q902	8-729-029-86	TRANSISTOR DTC124ESA	
Q903	8-729-107-78	TRANSISTOR 2SC3623-K	
RESISTOR			
R401	1-249-425-11	CARBON	4.7K 5% 1/4W
R407	1-215-447-00	METAL	12K 1% 1/4W
R408	1-249-383-11	CARBON	1.5 5% 1/4W F
R410	1-215-859-00	METAL OXIDE	22 5% 1W F
R411	1-215-445-00	METAL	10K 1% 1/4W
R412	1-215-421-00	METAL	1K 1% 1/4W
R418	1-214-798-21	METAL	1.8 1% 1/2W
R420	1-215-461-00	METAL	47K 1% 1/4W
R421	1-214-798-21	METAL	1.8 1% 1/2W
R422	1-215-866-11	METAL OXIDE	330 5% 1W F
R423	1-215-439-00	METAL	5.6K 1% 1/4W
R424	1-215-447-00	METAL	12K 1% 1/4W
R425	1-215-441-00	METAL	6.8K 1% 1/4W
R426	1-249-383-11	CARBON	1.5 5% 1/4W F
R427	1-215-447-00	METAL	12K 1% 1/4W
R500	1-249-405-11	CARBON	100 5% 1/4W F
R501	1-247-863-91	CARBON	22K 5% 1/4W
R503	1-249-437-11	CARBON	47K 5% 1/4W
R504	1-215-888-00	METAL OXIDE	220 5% 2W F
R505	1-247-863-91	CARBON	22K 5% 1/4W



Note: The components identified by shading and mark Δ are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un trame et une marque Δ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifique.

REF.NO.	PART NO.	DESCRIPTION		REMARK		REF.NO.	PART NO.	DESCRIPTION		REMARK
R506	1-216-391-11	METAL OXIDE	1.5	5%	3W F	R552	1-249-385-11	CARBON	2.2	5% 1/4W F
R507	1-249-437-11	CARBON	47K	5%	1/4W	R553	1-249-421-11	CARBON	2.2K	5% 1/4W
R508	1-216-391-11	METAL OXIDE	1.5	5%	3W F	R554	1-249-421-11	CARBON	2.2K	5% 1/4W
R509	1-249-389-11	CARBON	4.7	5%	1/4W F	R555	1-249-377-11	CARBON	0.47	5% 1/4W F
R510	1-249-389-11	CARBON	4.7	5%	1/4W	R556	1-202-818-00	SOLID	1K	20% 1/2W
R511	1-249-401-11	CARBON	47	5%	1/4W	R563	1-249-421-11	CARBON	2.2K	5% 1/4W
R512	1-247-881-00	CARBON	120K	5%	1/4W	R564	1-249-421-11	CARBON	2.2K	5% 1/4W
R513	1-249-429-11	CARBON	10K	5%	1/4W	R565	1-215-483-00	METAL	390K	1% 1/4W
R514	1-249-429-11	CARBON	10K	5%	1/4W	R567	1-215-880-00	METAL OXIDE	10	5% 2W F
R515	1-215-481-00	METAL	330K	1%	1/4W	R598	1-215-453-00	METAL	22K	1% 1/4W
R517	1-249-417-11	CARBON	1K	5%	1/4W F	R599	1-215-467-00	METAL	82K	1% 1/4W
R518	1-249-417-11	CARBON	1K	5%	1/4W F	R601 Δ	1-202-847-00	SOLID	560K	20% 1/2W
R519	1-249-437-11	CARBON	47K	5%	1/4W	R602 Δ	1-205-998-11	WIREWOUND	1	5% 10W
R520	1-249-417-11	CARBON	1K	5%	1/4W F	R603 Δ	1-202-933-61	FUSIBLE	0.1	10% 1/2W F
R521	1-249-389-11	CARBON	4.7	5%	1/4W F	R604	1-215-926-00	METAL OXIDE	33K	5% 3W F
R522	1-249-417-11	CARBON	1K	5%	1/4W F	R605	1-249-437-11	CARBON	47K	5% 1/4W
R523	1-249-377-11	CARBON	0.47	5%	1/4W F	R606	1-249-417-11	CARBON	1K	5% 1/4W
R524	1-216-447-00	METAL OXIDE	27	5%	2W F	R607	1-247-791-91	CARBON	22	5% 1/4W
R525	1-249-426-11	CARBON	5.6K	5%	1/4W	R608	1-249-429-11	CARBON	10K	5% 1/4W
R526	1-249-377-11	CARBON	0.47	5%	1/4W F	R609	1-216-381-11	METAL OXIDE	0.22	5% 3W F
R527	1-215-913-11	METAL OXIDE	220	5%	3W F	R610	1-215-925-11	METAL OXIDE	22K	5% 3W F
R528	1-215-910-00	METAL OXIDE	68	5%	3W F	R611	1-247-885-00	CARBON	180K	5% 1/4W
R529	1-249-441-11	CARBON	100K	5%	1/4W	R612	1-249-431-11	CARBON	15K	5% 1/4W
R530	1-216-474-11	METAL OXIDE	82	5%	3W F	R613	1-249-411-11	CARBON	330	5% 1/4W
R531	1-216-474-11	METAL OXIDE	82	5%	3W F	R614	1-249-421-11	CARBON	2.2K	5% 1/4W
R532	1-249-389-11	CARBON	4.7	5%	1/4W F	R615	1-249-377-11	CARBON	0.47	5% 1/4W F
R533 Δ	1-215-488-00	METAL	620K	1%	1/4W	R619	1-249-425-11	CARBON	4.7K	5% 1/4W
R534 Δ	1-215-468-00	METAL	91K	1%	1/4W	R621	1-249-434-11	CARBON	27K	5% 1/4W
R535 Δ	1-215-473-00	METAL	150K	1%	1/4W	R623	1-215-445-00	METAL	10K	1% 1/4W
R536	1-249-428-11	CARBON	8.2K	5%	1/4W	R631	1-215-405-00	METAL	220	1% 1/4W
R537	1-249-397-11	CARBON	22	5%	1/4W F	R651	1-215-878-00	METAL OXIDE	33K	5% 1W F
R538	1-215-441-00	METAL	6.8K	1%	1/4W	R652 Δ	1-211-874-11	FUSIBLE	0.12	10% 1/2W
R539	1-215-476-00	METAL	200K	1%	1/4W	R654 Δ	1-219-154-11	FUSIBLE	0.12	10% 1/4W
R540	1-215-457-00	METAL	33K	1%	1/4W	R655	1-249-417-11	CARBON	1K	5% 1/4W
R541	1-215-443-00	METAL	8.2K	1%	1/4W	R656	1-249-417-11	CARBON	1K	5% 1/4W
R542 Δ	1-215-429-00	METAL	2.2K	1%	1/4W	R657	1-249-429-11	CARBON	10K	5% 1/4W
R543 Δ	1-215-429-00	METAL	2.2K	1%	1/4W	R658	1-215-417-00	METAL	680	1% 1/4W
R544 Δ	1-215-463-00	METAL	56K	1%	1/4W	R659	1-215-483-00	METAL	390K	1% 1/4W
R545 Δ	1-215-461-00	METAL	47K	1%	1/4W	R660	1-215-443-00	METAL	8.2K	1% 1/4W
R546	1-249-397-11	CARBON	22	5%	1/4W F	R661	1-247-895-91	CARBON	470K	5% 1/4W
R547	1-249-424-11	CARBON	3.9K	5%	1/4W	R662	1-215-457-00	METAL	33K	1% 1/4W
R548	1-215-437-00	METAL	4.7K	1%	1/4W	R663	1-249-429-11	CARBON	10K	5% 1/4W
R549	1-215-880-00	METAL OXIDE	10	5%	2W F	R664	1-216-352-11	METAL OXIDE	1.8	5% 1W F
R550	1-249-429-11	CARBON	10K	5%	1/4W	R665	1-249-429-11	CARBON	10K	5% 1/4W
R551	1-215-423-00	METAL	1.2K	1%	1/4W	R666	1-249-429-11	CARBON	10K	5% 1/4W
						R667 Δ	1-211-881-11	FUSIBLE	0.47	10% 1/2W
						R670	1-249-417-11	CARBON	1K	5% 1/4W



Note: The components identified by shading and mark **Δ** are critical for safety. Replace only with part number specified.

Note: Les composants identifiés par un trame et une marque **Δ** sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

REF.NO.	PART NO.	DESCRIPTION	REMARK	REF.NO.	PART NO.	DESCRIPTION	REMARK
R671	1-249-417-11	CARBON	1K 5% 1/4W	R931	1-249-428-11	CARBON	8.2K 5% 1/4W
R672	1-249-403-11	CARBON	68 5% 1/4W	R932	1-249-428-11	CARBON	8.2K 5% 1/4W
R673	1-249-429-11	CARBON	10K 5% 1/4W	R933	1-249-431-11	CARBON	15K 5% 1/4W
R674	1-249-429-11	CARBON	10K 5% 1/4W	R934	1-249-429-11	CARBON	10K 5% 1/4W
R801	1-249-377-11	CARBON	0.47 5% 1/4W F	R935	1-249-428-11	CARBON	8.2K 5% 1/4W
R807	1-249-438-11	CARBON	56K 5% 1/4W	R936	1-249-425-11	CARBON	4.7K 5% 1/4W
R808	1-215-485-00	METAL	470K 1% 1/4W	R937	1-249-428-11	CARBON	8.2K 5% 1/4W
R809	1-215-483-00	METAL	390K 1% 1/4W	R938	1-249-428-11	CARBON	8.2K 5% 1/4W
R811	1-249-432-11	CARBON	18K 5% 1/4W	R939	1-249-417-11	CARBON	1K 5% 1/4W
R815	1-215-457-00	METAL	33K 1% 1/4W	R940	1-249-434-11	CARBON	27K 5% 1/4W
R817	1-215-461-00	METAL	47K 1% 1/4W	R941	1-249-428-11	CARBON	8.2K 5% 1/4W
R819	1-215-457-00	METAL	33K 1% 1/4W	R942	1-249-434-11	CARBON	27K 5% 1/4W
R820	1-215-455-00	METAL	27K 1% 1/4W	R943	1-249-428-11	CARBON	8.2K 5% 1/4W
R821	1-215-465-00	METAL	68K 1% 1/4W	R944	1-249-424-11	CARBON	3.9K 5% 1/4W
R822	1-215-471-00	METAL	120K 1% 1/4W	R945	1-249-424-11	CARBON	3.9K 5% 1/4W
R823	1-215-481-00	METAL	330K 1% 1/4W	R946	1-247-903-00	CARBON	1M 5% 1/4W
R824	1-249-429-11	CARBON	10K 5% 1/4W	R947	1-247-883-00	CARBON	150K 5% 1/4W
R825	1-259-878-11	CARBON	1.5M 5% 1/4W	R948	1-247-883-00	CARBON	150K 5% 1/4W
R830	1-215-461-00	METAL	47K 1% 1/4W	R949	1-247-883-00	CARBON	150K 5% 1/4W
R831	1-215-405-00	METAL	220 1% 1/4W	R950	1-247-883-00	CARBON	150K 5% 1/4W
R900	1-249-417-11	CARBON	1K 5% 1/4W	R951	1-247-883-00	CARBON	150K 5% 1/4W
R901	1-249-425-11	CARBON	4.7K 5% 1/4W	R952	1-247-883-00	CARBON	150K 5% 1/4W
R902	1-249-425-11	CARBON	4.7K 5% 1/4W	R954	1-249-425-11	CARBON	4.7K 5% 1/4W
R903	1-249-425-11	CARBON	4.7K 5% 1/4W	R955	1-215-478-00	METAL	240K 1% 1/4W
R904	1-249-425-11	CARBON	4.7K 5% 1/4W	R956	1-249-421-11	CARBON	2.2K 5% 1/4W
R905	1-249-425-11	CARBON	4.7K 5% 1/4W	R957	1-215-441-00	METAL	6.8K 1% 1/4W
R906	1-215-449-00	METAL	15K 1% 1/4W	R958	1-249-420-11	CARBON	1.8K 5% 1/4W
R907	1-249-417-11	CARBON	1K 5% 1/4W	R959	1-249-428-11	CARBON	8.2K 5% 1/4W
R908	1-249-425-11	CARBON	4.7K 5% 1/4W	R960	1-249-425-11	CARBON	4.7K 5% 1/4W
R909	1-249-437-11	CARBON	47K 5% 1/4W	R962	1-249-429-11	CARBON	10K 5% 1/4W
R910	1-247-895-91	CARBON	470K 5% 1/4W	R963	1-249-429-11	CARBON	10K 5% 1/4W
R911	1-249-431-11	CARBON	15K 5% 1/4W	R964	1-247-883-00	CARBON	150K 5% 1/4W
R912	1-249-413-11	CARBON	470 5% 1/4W	R965	1-249-415-11	CARBON	680 5% 1/4W
R914	1-249-421-11	CARBON	2.2K 5% 1/4W	R966	1-247-895-91	CARBON	470K 5% 1/4W
R915	1-249-417-11	CARBON	1K 5% 1/4W	R968	1-247-883-00	CARBON	150K 5% 1/4W
R916	1-249-417-11	CARBON	1K 5% 1/4W	R972	1-249-429-11	CARBON	10K 5% 1/4W
R917	1-249-417-11	CARBON	1K 5% 1/4W	R973	1-249-429-11	CARBON	10K 5% 1/4W
R918	1-249-435-11	CARBON	33K 5% 1/4W	R975	1-249-429-11	CARBON	10K 5% 1/4W
R919	1-249-425-11	CARBON	4.7K 5% 1/4W	R976	1-249-425-11	CARBON	4.7K 5% 1/4W
R920	1-249-417-11	CARBON	1K 5% 1/4W	R977	1-249-417-11	CARBON	1K 5% 1/4W
R921	1-247-863-91	CARBON	22K 5% 1/4W	R979	1-249-432-11	CARBON	18K 5% 1/4W
R924	1-249-434-11	CARBON	27K 5% 1/4W	R980	1-247-883-00	CARBON	150K 5% 1/4W
R925	1-249-432-11	CARBON	18K 5% 1/4W	R981	1-249-413-11	CARBON	470 5% 1/4W
R926	1-249-434-11	CARBON	27K 5% 1/4W	R983	1-215-467-00	METAL	82K 1% 1/4W
R927	1-249-434-11	CARBON	27K 5% 1/4W	R984	1-249-417-11	CARBON	1K 5% 1/4W
R928	1-249-434-11	CARBON	27K 5% 1/4W	R985	1-247-807-31	CARBON	100 5% 1/4W
R929	1-249-436-11	CARBON	39K 5% 1/4W	R986	1-215-445-00	METAL	10K 1% 1/4W
R930	1-249-434-11	CARBON	27K 5% 1/4W	R987	1-249-425-11	CARBON	4.7K 5% 1/4W
				R989	1-249-429-11	CARBON	10K 5% 1/4W



Note: The components identified by shading and mark **Δ** are critical for safety. Replace only with part number specified.

Note: The components identified by **⊠** in this manual have been carefully factory-selected for each set in order to satisfy regulations regarding X-ray radiation. Should replacement be required, replace only with the value originally used.

REF.NO.	PART NO.	DESCRIPTION	REMARK
R990	1-247-807-31	CARBON	100 5% 1/4W
R991	1-247-807-31	CARBON	100 5% 1/4W
R992	1-249-417-11	CARBON	1K 5% 1/4W
R993	1-249-429-11	CARBON	10K 5% 1/4W
R994	1-249-417-11	CARBON	1K 5% 1/4W
R995	1-249-413-11	CARBON	470 5% 1/4W
R996	1-249-429-11	CARBON	10K 5% 1/4W
R997	1-249-417-11	CARBON	1K 5% 1/4W
R998	1-249-429-11	CARBON	10K 5% 1/4W
R999	1-249-413-11	CARBON	470 5% 1/4W
R1801	1-215-433-00	METAL	3.3K 1% 1/4W
R1806	1-215-421-00	METAL	1K 1% 1/4W
R1810	1-215-413-00	METAL	470 1% 1/4W
R1811	1-215-409-00	METAL	330 1% 1/4W
R1812	1-215-413-00	METAL	470 1% 1/4W
R1813	1-215-413-00	METAL	470 1% 1/4W
R1814	1-215-417-00	METAL	680 1% 1/4W
R1815	1-215-469-00	METAL	100K 1% 1/4W
R1818	1-215-425-00	METAL	1.5K 1% 1/4W
R1819	1-215-425-00	METAL	1.5K 1% 1/4W
R1820	1-215-433-00	METAL	3.3K 1% 1/4W
R1822	1-215-433-00	METAL	3.3K 1% 1/4W
R1823	1-215-413-00	METAL	470 1% 1/
R1832	1-215-469-00	METAL	100K 1% 1/4W
VARIABLE RESISTOR			
⊠ RV501	Δ 1-241-767-21	RES, ADJ, CERMET 100K	
	4-060-176-01	COVER, VOLUME 6 MOLD (FOR RV501)	
RELAY			
RY601	Δ 1-755-031-11	RELAY	
SWITCH			
S1801	1-692-431-21	SWITCH, TACTILE	
S1802	1-692-431-21	SWITCH, TACTILE	
S1803	1-692-431-21	SWITCH, TACTILE	
S1809	1-692-431-21	SWITCH, TACTILE	
S1815	1-692-220-11	SWITCH, TACTILE	
S1816	1-692-220-11	SWITCH, TACTILE	
S1817	1-692-220-11	SWITCH, TACTILE	
S1818	1-692-220-11	SWITCH, TACTILE	

REF.NO.	PART NO.	DESCRIPTION	REMARK
S1821	1-692-431-21	SWITCH, TACTILE	
SPARK GAP			
SG501	Δ 1-519-422-11	GAP, SPARK	
TRANSFORMER			
T501	Δ 1-453-240-21	TRANSFORMER ASSY, FLYBACK (NX-4130//JIE4)	
T503	1-429-109-11	TRANSFORMER, FERRITE (DFT)	
T504	Δ 1-431-248-11	TRANSFORMER, HORIZONTAL DRIVE	
T505	1-429-211-11	TRANSFORMER, FERRITE (HST)	
T601	Δ 1-431-247-11	TRANSFORMER, CONVERTER (SRT)	
THERMISTOR			
TH501	1-807-796-11	THERMISTOR	
TH601	Δ 1-809-827-11	THERMISTOR	
TH602	Δ 1-809-827-11	THERMISTOR, POSITIVE	
VARISTOR			
VA601	Δ 1-810-622-11	VARISTOR	
CRYSTAL			
X900	1-567-890-11	VIBRATOR, CRYSTAL	
MISCELLANEOUS			
Δ 1-416-282-21		COIL, DEMAGNETIZATION	
Δ 1-452-923-21		NECK ASSY (NA-2914)	
1-543-653-11		CORE ASSY, BEAD (DIVISION TYPE)	
Δ 1-558-481-11		CORD SET, POWER (CPD-200ES SH)	
Δ 1-765-717-11		CORD SET, POWER (CPD-200ES EQ)	
4-060-155-01		HOLDER, HV CABLE	
3-860-654-01		MANUAL, INSTRUCTION	
Δ 8-451-487-11		DY Y17FRG-M	
Δ 1-453-240-21		TRANSFORMER ASSY, FLYBACK(NX-4103//JIE4)	
Δ 8-738-728-05		CRT, 17FRFM (CPD-200ES SH)	
Δ 8-738-733-05		CRT, 17FRFM (CPD-200ES EQ)	
Δ 8-738-728-82		ITC ASSY (17FRFM-RS3) (CPD-200ES SH)	
Δ 8-738-733-82		ITC ASSY (17FRFM-R2) (CPD-200ES EQ)	
4-060-206-01		DISK, WINDOWS 95	

Sony Corporation

Sony Technology Center
Product Quality Division

Service Promotion Department

<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>	<u>REMARK</u>	<u>REF.NO.</u>	<u>PART NO.</u>	<u>DESCRIPTION</u>	<u>REMARK</u>
----------------	-----------------	--------------------	---------------	----------------	-----------------	--------------------	---------------