

MIS CARD (090-44018-05 & 090-45018-05)
SOFTWARE RELEASE DOCUMENT
RELEASE 5.04.01

CONTENTS	PAGE
1. GENERAL	1
2. NEW FEATURES	1
3. CORRECTED ISSUES	1
4. KNOWN ISSUES	2
5. ESTIMATED DOWN TIME	2
6. ESTIMATED INSTALLATION TIME	2
7. REQUIREMENTS	2
A. Hardware	2
B. Software	2
C. Documentation	2
8. INSTALLATION	2
Charts	
1. Software Installation Procedure	3

1. GENERAL

1.01 This document provides information about Release 5.04.01 of the software for Symmetricom's MIS card (part numbers 090-44018-05 and 090-45018-05).

1.02 Whenever this document is reissued, the reason for reissue will be given in this paragraph.

2. NEW FEATURES

2.01 This release of the MIS card software includes the following new features:

- Support was added for the following cards:

DCIM-T	EA10M
DCIM-EA	EA20M
TOTA-M	

- Support was added for synchronization status messages (SSM) including modifying some existing commands and adding the following new commands:

ED-SSM-EQPT
RTRV-SSM-EQPT
ED-SSM-PORT
RTRV-SSM-PORT
RTRV-MSG-EQPT
RTRV-MSG-PORT
SET-TH-MSG
RTRV-TH-MSG

3. CORRECTED ISSUES

3.01 This release of the MIS card software includes the following corrections:

- *Issue 8-02:* When the CPY-MEM command was used to copy information from the cards in an expansion shelf to the MIS card, a COMPLD was not returned.

Correction: When the CPY-MEM command is used to copy information from the cards in an expansion shelf to the MIS card, a COMPLD is returned.

4. KNOWN ISSUES

4.01 There are no known issues in this release.

5. ESTIMATED DOWN TIME

5.01 Not applicable.

6. ESTIMATED INSTALLATION TIME

6.01 Approximately 1 hour is required to install this software release.

7. REQUIREMENTS

7.01 The hardware, software, and documentation required to operate this software release is listed below.

A. Hardware

7.02 An MIS card (part number 090-44018-05 or 090-45018-05) must be installed in the shelf to receive this software release.

7.03 Some cards have specific software revision (listed on the card front panel) requirements in order to be compatible with this software release. Table A lists the cards, including part number, and the software revision required. Cards with higher revisions can also be used.

B. Software

7.04 No additional software is required for this software release.

C. Documentation

7.05 Use either of the manuals / revisions listed below. Higher revision manuals can also be used.

<u>Manual</u>	<u>Part Number</u>	<u>Revision</u>
TL1 User's Guide	997-44018-07	A
TL1 User's Guide	997-45018-07	A

8. INSTALLATION

8.01 To install this software release from a floppy disk, follow the procedure in Chart 1. Repeat the procedure in Chart 1 for *each* shelf where this software is to be installed.

Table A. Card Requirements

CARD	PART NUMBER	SOFTWARE REVISION
Version 5 MRC-EA	090-45010-56	B
Version 5 MRC-EA/C	090-44010-56	B
Version 5 MRC-T	090-45010-53	B
Version 5 TO-EA5	090-45029-51	C
Version 5 TO-EA5/C	090-44029-51	D
Version 5 TOTA-5	090-45012-52	D
GTI	090-42140-13	E
GTI	090-42140-14	E
GTI	090-42140-15	B
GTI	090-44140-14	E

Chart 1. Software Installation Procedure

STEP	PROCEDURE
<p>This chart provides the steps for copying an MIS card program from an external source to the MIS card.</p> <p>Prerequisites:</p> <ol style="list-style-type: none"> 1. The MIS card to which the software will be downloaded has a part number of 090-44018-05 or 090-45018-05. 2. The PC from which this software will be installed is running in a VT100 terminal mode. 3. The PC from which this software will be installed is running a commercial software communication package (such as PROCOMM PLUS®) that supports the KERMIT protocol. 4. The PC from which this software will be installed must be connected to any available communications port on the shelf where the MIS card resides. 	
1	<p>Create a directory on the hard drive of the PC, and copy the files from both disks (092-45118-41 and 092-45218-41) to the newly created directory.</p>
2	<p>Access level 1 is required to use the command in this step. Determine the setting for echo on the communication port to be used by entering the following:</p> <pre>RTRV-COM:[<tid>]:<aid>:<ctag>;</pre> <p>aid = communication port to be used to copy the program:</p> <ul style="list-style-type: none"> COM-1 = communication port 1 (backplane D connector) COM-2 = communication port 2 (backplane D connector or front panel RJ connector) COM-3 = communication port 3 (backplane D connector) <p>Response:</p> <pre><sid> <date> <time> M <ctag> COMPLD "<aid>" /*BAUD=<value>,MONMSG=<value>,KEEPALIVE=<value>, COMTYPE=<value>,ENDOFTEXT=<value>,ECHO=<value>, COMPRI=<value>,HWCONTROL=<value>, SWCONTROL=<value>,DUR=<value> ...*/</pre> <p>where the value for the echo parameter is ALW or INH.</p>

Chart 1. Software Installation Procedure (Contd)

STEP	PROCEDURE
3	<p>Access level 3 is required to use the command in this step. If the echo parameter is set to INH (inhibited), skip to the next step. If the echo parameter is set to ALW (allowed), set the echo to INH by entering:</p> <pre>ED-COM: [<tid>]:<aid>:<ctag>::,,,,,INH,,,,;</pre> <p>aid = communication port to be used to copy the program: COM-1 = communication port 1 (backplane D connector) COM-2 = communication port 2 (backplane D connector or front panel RJ connector) COM-3 = communication port 3 (backplane D connector)</p> <p>Response:</p> <pre><sid> <date> <time> M <ctag> COMPLD</pre>
4	<p>Access level 2 is required to use the command in this step. Determine which program location (HI BANK or LOW BANK) is active (ACTIVE) in the MIS card by entering:</p> <pre>RTRV-INVENTORY: [<tid>]:<aid>:<ctag>;</pre> <p>aid = ADMIN</p> <p>Response:</p> <pre><sid> <date> <time> M <ctag> COMPLD "<aid>" /* CARD=<value>, TYPE=<value>, PART=<value>, CLEI=<value>, SERIAL=<value>, HARDREV=<value>, LOW_BANK_SW=<value>: SOFTREV=<value>, SOFTVER=<value>, HI_BANK_SW=<value>: SOFTREV=<value>, SOFTVER=<value> */</pre> <p>where the value for either the LOW_BANK_SW or the HI_BANK_SW is ACTIVE (the active status will be used later in this procedure).</p>

Chart 1. Software Installation Procedure (Contd)

STEP	PROCEDURE																		
5	Set the KERMIT protocol parameters as follows: <table style="margin-left: 40px;"> <tr><td>Control quote:</td><td>35</td></tr> <tr><td>Pad:</td><td>0</td></tr> <tr><td>End of line:</td><td>13</td></tr> <tr><td>8th bit quote:</td><td>38</td></tr> <tr><td>Block start:</td><td>1</td></tr> <tr><td>Maximum packet size:</td><td>512</td></tr> <tr><td>Number of pad characters:</td><td>0</td></tr> <tr><td>File type:</td><td>Binary</td></tr> <tr><td>Block check type:</td><td>3-byte CRC</td></tr> </table>	Control quote:	35	Pad:	0	End of line:	13	8th bit quote:	38	Block start:	1	Maximum packet size:	512	Number of pad characters:	0	File type:	Binary	Block check type:	3-byte CRC
Control quote:	35																		
Pad:	0																		
End of line:	13																		
8th bit quote:	38																		
Block start:	1																		
Maximum packet size:	512																		
Number of pad characters:	0																		
File type:	Binary																		
Block check type:	3-byte CRC																		
6	Access level 4 is required to use the command in this step. Enter: <pre style="margin-left: 40px;">CPY-MEM:[<tid>]::<ctag>::,FROM-EXT,,TO-MIS:PGM;</pre> Response: <pre style="margin-left: 40px;"><sid> <date> <time> M <ctag> COMPLD</pre>																		
7	<p>Caution: If the program download is interrupted before completion, the inactive bank will be empty. Any program residing in the inactive bank will be lost. Do not interrupt the download.</p> <p>Transmit one of the following files from the directory created in Step 5 to the inactive memory bank in the MIS card:</p> <p>If the LOW BANK is active (as determined in Step 4), transmit the HI file (which has a file-name in the format of <xxxxxx.HI).</p> <p>If the HI BANK is active (as determined in Step 4), transmit the LOW file (which has a file-name in the format of <xxxxxx.LOW).</p>																		
8	Wait until the communication software indicates that the copying has been completed (may take up to 8 minutes).																		
9	Access level 5 is required to use the command in this step. To cause the MIS card to use the program just copied to the MIS card, the active program must be switched by entering the following command: <pre style="margin-left: 40px;">INIT-SYS:[<tid>]:<aid>:<ctag>::5; aid = MIS</pre> Response: <pre style="margin-left: 40px;"><sid> <date> <time> M <ctag> COMPLD</pre>																		
10	This procedure is completed.																		