

# **6602B Pulse Distribution**

***User Guide***

*Revision A - April 2004*

*Part Number 15248-201*



# Table of Contents

## About this User Guide

Purpose .....	1
Conventions .....	1
Special Notices .....	2
Symmetricon Limited Product Warranty .....	3

## Introduction

Overview .....	5
Purpose of Equipment .....	5
Instrument Identification .....	5
Preparation for Shipment .....	5

## Installation

Mounting .....	7
Power Connection/Fuses/Voltage .....	7
DC Power Connection .....	8
Signal Connectors .....	8
Daisy Chaining More Than One Module .....	9
Alarm Connections .....	9

## Operation

Overview .....	11
Controls and Indicators .....	11
HI Z/50W .....	11
ALARM OVERRIDE .....	11
POWER .....	11
ALARM .....	12
INPUT FAULT .....	12
OUTPUT FAULT .....	12

## Specifications

1 PPS Outputs (10) .....	13
1 PPS Input .....	13
Power .....	13
Mechanical .....	14
Environment .....	14
Alarm Indication .....	14
Controls and Indicators .....	14
Available Versions .....	14

## Customer Assistance

US Assistance Center .....	15
EMEA Assistance Center .....	15

**Index**

Numerics .....	17
A .....	17
C .....	17
D .....	17
E .....	17
F .....	17
H .....	17
I .....	17
M .....	17
N .....	18
O .....	18
P .....	18
R .....	18
S .....	18
V .....	18
W .....	18

# About this User Guide

## Purpose

---

The 6602B User Guide describes the procedures for unpacking, installing, using, maintaining, and troubleshooting the 6602B.

## Conventions

---

This guide uses the following conventions:

- **Acronyms and Abbreviations** – Terms are spelled out the first time they appear in text. Thereafter, only the acronym or abbreviation is used.
- **Revision Control** – The title page lists the printing date and versions of the product this guide describes.
- **Typographical Conventions** – This guide uses the typographical conventions described in the table below.

When text appears this way...	... it means:
<i>TimeProvider User's Guide</i>	The title of a document.
SSU CRITICAL	An operating mode, alarm state, status, or chassis label.
Select <b>File</b> , <b>Open</b> ...	Click the Open option on the File menu.
Press <b>Enter</b> Press ;	A named keyboard key. The key name is shown as it appears on the keyboard. An explanation of the key's acronym or function immediately follows the first reference to the key, if required.
6502 Username:	Text in a source file or a system prompt or other text that appears on a screen.
A <i>re-timing</i> application	A word or term being emphasized.
Symmetricom <b>does not</b> recommend...	A word or term given special emphasis.

## Special Notices

---

Warnings, Cautions, Recommendations, and Notes attract attention to essential or critical information in this guide. The types of information included in each are explained in the following examples.



**Warning:** To avoid serious personal injury or death, *do not* disregard warnings. All warnings use this symbol. Warnings are installation, operation, or maintenance procedures, practices, or statements, that if not strictly observed, may result in serious personal injury or even death.

---



**Caution:** To avoid personal injury, *do not* disregard cautions. All cautions use this symbol. Cautions are installation, operation, or maintenance procedures, practices, conditions, or statements, that if not strictly observed, may result in damage to, or destruction of, the equipment. Cautions are also used to indicate a long-term health hazard.

---



**ESD Caution:** To avoid personal injury and electrostatic discharge (ESD) damage to equipment, *do not* disregard ESD cautions. All ESD cautions use this symbol. ESD cautions are installation, operation, or maintenance procedures, practices, conditions, or statements that if not strictly observed, may result in possible personal injury, electrostatic discharge damage to, or destruction of, static sensitive components of the equipment.

---



**Electrical Shock Caution:** To avoid electrical shock and possible personal injury, do not disregard electrical shock cautions. All electrical shock cautions use this symbol. Electrical shock cautions are practices, procedures, or statements, that if not strictly observed, may result in possible personal injury, electrical shock damage to, or destruction of components of the equipment.

---



**Recommendation:** All recommendations use this symbol. Recommendations indicate manufacturer-tested methods or known functionality. Recommendations contain installation, operation, or maintenance procedures, practices, conditions, or statements, that provide important information for optimum performance results.

---



**Note:** All notes use this symbol. Notes contain installation, operation, or maintenance procedures, practices, conditions, or statements, that alert you to important information, which may make your task easier or increase your understanding.

---

## Symmetricom Limited Product Warranty

---

1. Hardware and embedded software - For a period of one (1) year from date of shipment by Symmetricom, Symmetricom warrants that all Products shall be free from defects in design, material, and workmanship; shall conform to and perform in accordance with Symmetricom's published specifications, if any; shall be free and clear of any liens and encumbrances; and shall have good and valid title. This warranty will survive inspection, acceptance, and payment by Buyer. Symmetricom does not warrant that the operation of such Product will be uninterrupted or error free. This warranty does not cover failures caused by acts of God, electrical or environmental conditions; abuse, negligence, accident, loss or damage in transit; or improper site preparation.

This warranty shall be null and void in the event (i) Buyer or any third party attempts repair of the goods without Symmetricom's advance written authorization, or (ii) defects are the result of improper or inadequate maintenance by Buyer or third party; (iii) of damage to said goods by Buyer or third party-supplied software, interfacing or supplies; (iv) of improper use (including termination of non-certified third party equipment on Symmetricom's proprietary interfaces and operation outside of the product's specifications) by Buyer or third party; or (v) the goods are shipped to any country other than that originally specified in the Buyer's purchase order.

Goods not meeting the foregoing warranty will be repaired or replaced, at Symmetricom's option, upon return to Symmetricom's factory freight prepaid; provided, however that Buyer has first obtained a return materials authorization number ("RMA Number") from Symmetricom authorizing such return. The RMA Number shall be placed on the exterior packaging of all returns. Symmetricom will pay shipping costs to return repaired or replacement goods to Buyer.

Symmetricom reserves the right to disallow a warranty claim following an inspection of returned product. When a warranty claim is questioned or disallowed, Symmetricom will contact Buyer by telephone or in writing to resolve the problem.

2. Software - Symmetricom warrants that for a period of ninety (90) days from date of shipment by Symmetricom the accompanying media will be free from defects in materials and workmanship under normal use. The physical media warranty does not apply to defects arising from misuse, theft, vandalism, fire, water, acts of God or other similar perils. Symmetricom will not be liable for any damages caused by the Buyer's failure to fulfill its responsibilities as stated above.

3. THE FOREGOING WARRANTY IS IN LIEU OF ALL OTHER WARRANTIES, EXPRESSED OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, ANY IMPLIED WARRANTIES OF TITLE, MERCHANTABILITY, OR FITNESS FOR A PARTICULAR PURPOSE HOWSOEVER ARISING.

4. Limitation of Liability - The remedies provided herein are the Buyer's sole and exclusive remedies. In no event or circumstances will Symmetricom be liable to Buyer for indirect, special, incidental or consequential damages, including without limitation, loss of revenues or profits, business interruption costs, loss of data or software restoration, or damages relating to Buyer's procurement of substitute products or services. Except for liability for personal injury or property damage arising from Symmetricom's negligence or willful misconduct, in no event will Symmetricom's total cumulative liability in connection with any order hereunder or Symmetricom's Goods, from all causes of action of any kind, including tort, contract, negligence, strict liability and breach of warranty, exceed the total amount paid by Buyer hereunder. SOME JURISDICTIONS DO NOT ALLOW CERTAIN LIMITATIONS OR EXCLUSIONS OF LIABILITY, SO THE ABOVE LIMITATIONS OR EXCLUSIONS MAY NOT APPLY TO ALL BUYERS.



# Introduction

## Overview

---

This manual contains the information needed to install, configure and use the Symmetricom 6602B.

The Symmetricom 6602B Pulse Distribution Module takes a single 1 PPS input, and provides ten additional 1 PPS buffered outputs per module.

## Purpose of Equipment

---

Symmetricom's 6602B Pulse Distribution Module is a ten-channel, pulse distribution amplifier packaged in a 1U (1.75" high) rack mount chassis. The 6602B buffers and provides one pulse per second signal distribution to ten separate locations. The module's summary fault alarm output feature indicates an alarm whenever there is a single output fault condition.

The 6602B preserves input phase characteristics over a wide range of environmental conditions. A daisy chain of up to ten Symmetricom 6602B modules provides up to 100 output signals or with each output of one module as the input signal for other modules it provides almost infinite expansion capability with minimal signal degradation.

## Instrument Identification

---

The model number 6602B may be followed by a slash (/) and a three-digit number to indicate an option that is supplied within the instrument.

## Preparation for Shipment

---

To turn off the Symmetricom 6602B prior to shipment, remove the AC power from the plug on the rear panel. Package the instrument in its original packing if possible. If the original packing materials are not available, pack in a reinforced cardboard carton using foam to take up any space inside the carton. Do not use foam popcorn or crushed paper for packing.

If the instrument is being returned to Symmetricom, contact Symmetricom Customer Assistance. See "Customer Assistance" on page 15.



# Installation

## Mounting

---

The Symmetricom 6602B is designed to be mounted in a standard 19-inch equipment rack and takes up 1U of vertical space (1.75"). The chassis depth is 12 inches.

## Power Connection/Fuses/Voltage

---

The Symmetricom 6602B is powered from an AC source by a detachable power supply cord. The power cord is the disconnect device. Refer to Chapter Four for power supply requirements. The AC fuses are located inside the AC connector/filter. The hot and neutral lines are fused separately. To change fuses, refer to [Figure 2-1](#). Open the cover on the AC connector/filter by applying a screwdriver to the cover slot. Once the cover is open, each fuse holder may be removed for inspection or replacement. Replace only with a 0.2A, 250V as specified in Chapter four.




Figure 2-1 AC Input Filter/Fuses/Voltage Selector

The Symmetricom 6602B may be powered from 120 or 240 VAC. To change the AC input between 120 and 240 V, refer to Figure 2-1. Open the cover on the AC input connector by applying a screwdriver to the cover slot. Once the cover is open, a selector switch may be rolled left or right to line up "120" or "240" with the small window in the connector cover. Replace the cover on the AC input connector by snapping it in place.



**Caution:** Do not use the voltages labeled "100" or "230", as they are not connected.

---

## DC Power Connection

---

The Symmetricom 6602B (DC version) is powered from a DC source. The connections are made at TB1 as shown in [Figure 2-2](#). The voltage input may be 20 V to 75 V.




Figure 2-2 DC Power Connection

## Signal Connectors

---

Connect the signal to be distributed to one of the two BNC connectors labeled INPUT. Set the impedance switch to 50Ω (down) if only one 6602B module is to be used. If multiple 6602B modules are used to obtain more than 10 outputs, see [Figure 2-4](#).

Output cables may be connected in any order to the BNC connectors labeled 1 to 10. Refer to [Figure 2-3](#).





Figure 2-3 Signal Connections

With the 6602B powered, the green power indicator on the front panel will illuminate. The impedance switch should be set to 50Ω if there is only one module. The red indicator next to the input signal is off to show that there is a good input signal.

## Daisy Chaining More Than One Module

If more than ten outputs are required, up to ten Symmetricom 6602B modules can be driven by a common input signal to produce up to 100 outputs. [Figure 2-4](#) illustrates this connection.




*Figure 2-4 Daisy Chaining Multiple Modules*

The example in [Figure 2-4](#) shows three units. The original signal from the source is connected to the top IN connector on the right side of the first module. The lower IN connector on the first module is connected to the top IN connector on the second module. The second module is connected to the third module in the same fashion. The impedance switch for the first and second chassis is set to HI Z, while the impedance switch on the third (or last) chassis in the daisy chain is set to 50Ω.

## Alarm Connections

The Symmetricom 6602B provides for an alarm to signal the failure of any signal output. One set of form-C relay contacts is provided on the 9-pin D connector labeled ALARMS. For normal operation, pins 1 to 2 are open and pins 1 to 3 are closed. The sense is reversed for a fault condition. Refer to [Figure 2-5](#).



Relay shown in non-faulted condition

*Figure 2-5 Alarm Contacts*

If the input signal or input buffer fails or falls below the factory-set low-level threshold, the red fault indicator next to the input connector will turn on. Likewise, if any output buffer fails or falls below the low-level threshold, a red fault indicator next to that output will turn on. The ALARM form-C relay is normally energized, indicating no signal failure. If either the input or any output signal fails, the relay is de-energized (short between pins 1 and 2), indicating a fault condition. This is a fail-safe design that will indicate a fault in the event of a power loss.

# Operation

## Overview


---

The Symmetricom 6602B Pulse Distribution Module controls and indicators are described in this chapter.

Figure 3-1. 6602B Pulse Distribution Front Panel



Figure 3-2. 6602B Pulse Distribution Rear Panel



## Controls and Indicators

---

### HI Z/50Ω

This slide switch on the rear panel selects either the HI Z input impedance (unterminated) or the 50Ω input impedance. A 6602B installation of two or more (ten maximum) units will set the switch to HI Z position on the module connected to the source of the signal, and on all subsequent modules except the last module, which is switched to the 50Ω position, providing proper termination for the signal.

### ALARM OVERRIDE

When provided, the optional ALARM OVERRIDE toggle switch enables or disables the ALARM relay output on the ALARM connector. This makes ALARM OVERRIDE useful for suppressing audible alarms.

With ALARM OVERRIDE in the UP position, the ALARM relay is enabled and changes states in the event of a signal failure. With ALARM OVERRIDE in the DOWN position, the ALARM relay is disabled, forcing it into a normal (no alarm) condition. ALARM OVERRIDE doesn't affect the LED indicators.

### POWER

LED on the front panel to indicate that power is applied. There is no power switch on the 6602B. When power is connected, power is ON.

## **ALARM**

LED on the front panel to indicate that an ALARM condition exists. An alarm condition exists when the input signal or any output signal fails or falls below the factory preset amplitude.

## **INPUT FAULT**

This LED is located on the rear panel, just to the right of the lower INPUT connectors. If the input signal fails or falls below the factory preset amplitude, this LED will light and stay on until the cause of the fault is remedied.

## **OUTPUT FAULT**

There are ten LED indicators, located to the right of each output connector. If any output signal fails or falls below the factory preset amplitude, the LED associated with the failed output will light and stay on until the cause of the fault is remedied.



# Specifications



**Note:** All performance is at an ambient temperature of 25°C unless otherwise specified.

## 1 PPS Outputs (10)

---

Repetition Rate	1 PPS
Output Impedance	50Ω
Logic One	+4.5 volts minimum
Logic Zero	+0.8 volts maximum
Pulse Width	20 μS nominal
Rise Time	<5 nS
Fall Time	<5 nS
Propagation Delay	25 nS
Differential Delay	<9ns between any two outputs
Jitter	1 nS RMS
Connectors	BNC

## 1 PPS Input

---

Repetition Rate	1 PPS
Input Impedance	50Ω
Logic One	+2.7 to 10.0 volts
Logic Zero	+0.0 to 0.8 volts
Pulse Width	20 μs nominal
Rise Time	<5 nS
Fall Time	<5 nS
Connector	BNC

## Power

---

Operating Voltage	120/240 VAC, ±15%
Power	< 10W
DC Input (Optional)	22 to 56 VDC, 10 W Fuses 0.2 A, 250 V, fast acting, 5x20 mm (e.g., Littlefuse P/N 239.200)

## **Mechanical**

---

Height	1.75" (1 U)
Width	19" (including rack mount ears)
Depth	12"

## **Environment**

---

Operating Temperature	0 to 55°C
Relative Humidity	0 to 95%, non-condensing

## **Alarm Indication**

---

Summary alarm indicates failure of any output signal.

Front Panel	Red LED
Relay	Energized (short pins 1 & 3): No Failure De-energized (short pins 1 & 2): Failure

## **Controls and Indicators**

---

POWER	Green LED indicates power is connected
ALARM	Red LED indicates a signal output failure
ALARM OVERRIDE	Toggle Switch (option): Enable/disable audio alarm
HI Z/50Ω	Slide switch: Unterminated or 50Ω Terminated
INPUT FAULT	Red LED indicates fault with input signal
OUTPUT FAULT	Ten red LEDs indicate fault with output
See "Controls and Indicators" on page 11 for more information.	

## **Available Versions**

---

14369-101	Standard configuration, AC Input
Special Option	Standard configuration, DC Input
Special Option	Standard configuration, AC Input, w. Alarm Override

# Customer Assistance

For additional information about the products described in this guide, please contact your Symmetricom representative or your local sales office.

For Customer Assistance, please contact us by phone, e-mail, or on the web at [www.symmetricom.com/support/](http://www.symmetricom.com/support/).

## US Assistance Center

---

(United States and Canada, Latin America including Caribbean, Pacific Rim including Asia, Australia and New Zealand)

Tel +1 888 367 7966 (+1 888 FOR SYMM) or +1 408 428 7907 (Worldwide)

### **Customer Service**

For product quotes, service quotes, installations, order status and scheduling, 7:00 am to 5:00 pm Pacific Time, Monday through Friday, excluding U.S. Holidays.

### **Technical Support**

For technical support, 24 hours a day, 7 days a week, every day of the year: [support@symmetricom.com](mailto:support@symmetricom.com)

## EMEA Assistance Center

---

(Europe, Middle East and Africa)

Tel +49 700 32886435 or +1 408 428 7907 (Worldwide)

### **Customer Service**

For product quotes, service quotes, installations, order status and scheduling 8:00 am to 5:00 pm Central European Time, Monday through Friday, excluding Holidays.

### **Technical Support**

For technical support 24 hours a day, 7 days a week, every day of the year : [emeasupport@symmetricom.com](mailto:emeasupport@symmetricom.com)



# Index

## Numerics

1 PPS Input 13  
1 PPS Outputs (10) 13  
50 Ohms 11

## A

ALARM 12  
Alarm Connections 9  
Alarm Indication 14  
ALARM OVERRIDE 11  
Available Versions 14

## C

Caution 2  
Controls 11  
Controls and Indicators 14  
Customer Assistance 15

## D

Daisy Chaining More Than One Module 9  
DC Power Connection 8

## E

Electrical Shock Caution 2  
Environment 14  
ESD Caution 2

## F

FAULT 12  
Fuses 7

## H

HI Z 11

## I

Indicators 11, 14  
INPUT FAULT 12, 14  
Installation 7  
Instrument Identification 5  
Introduction 5

## M

Mechanical 14  
Mounting 7

Index

## **N**

Note 3

## **O**

Operation 11

OUTPUT FAULT 12

## **P**

POWER 11

Power 13

Power Connection 7

Purpose of Equipment 5

## **R**

Recommendation 2

## **S**

Shipment 5

Signal Connectors 8

Special Notices 2

Specifications 13

## **V**

Voltage 7

## **W**

Warning 2