

**FIELD SERVICE BULLETIN**

FSB# 098-41620-005

Date: January 7, 2004

2300 Orchard Parkway
San Jose, CA 95131-1017
Customer Assistance Center: 1-408-428-7907

System: XLi Time and Frequency System

Product Identity: **Product Code:**

XLi 1U **1510-602**

XLi 2U **1510-652**

Phone - Worldwide: 1-408-428-7907 (1) (3)

Toll free - North America: 1-888-367-7966 (1) (3)

Year Rollover When Using IRIG-B as a Time Source

When locked to IRIG-B as a time source, the year must be entered into the XLi to be correctly set after a year rollover. This applies to all software versions presently available.

Procedure:

This procedure uses Function 03 (Time and Date) to set the correct year on the XLi.

1. To eliminate any false time distribution, unlock the XLi from the IRIG-B source by disconnecting the time code cable. Make sure the unit reports the unlock condition before proceeding.
2. Select Function 03 on the keypad, via serial port, or via telnet.
3. After the time is displayed, the date is displayed. Change the year to 2004.
4. Save your changes.
5. Lock the XLi to the IRIG-B source by reconnecting the time code cable. Make sure the unit reports the lock condition.
6. Check the display for the correct year.