

Ref. No.	Part No.	Part Name & Description	Remarks	Ref. No.	Part No.	Part Name & Description	Remarks
D102	MA165	DIODE					
D401	MA4075MTA	DIODE	△	T701	RTP1N5E014-V	POWER TRANSFORMER (MAIN)	(E, EB, EG, EP) △
D601, 602	MA165	DIODE		T701	RTP1N5E015-V	POWER TRANSFORMER (MAIN)	(G) △
D603	MA700	DIODE		T701	RTP1N5E016-V	POWER TRANSFORMER (MAIN)	(GN) △
D605, 606	SB3606501T	DIODE		T751	RTP115E003-V	POWER TRANSFORMER (SUB)	(E, EB, EG, EP, GN) △
D609	MA165	DIODE		T751	RTP115E005-V	POWER TRANSFORMER (SUB)	(G) △
D651	MA165	DIODE					
D652	MA4056MTA	DIODE				COMPONENT COMBINATION (S)	
D653	MA165	DIODE					
D701-704	P300D5002T	DIODE	△	Z101	RLA6Z005M-T	COMPONENT COMBINATION	(E, EB, EP, G, GN)
D707, 708	MA4062MTA	DIODE	△	Z101	RLA2Z002M-T	COMPONENT COMBINATION	(EG)
D710	MA4220MTA	DIODE	△	Z102	RL1Z2006M-T	COMPONENT COMBINATION	
D712	MA4160M	DIODE	△	Z891	RCDHC-278N	REMOTE SENSOR	
D721-724	P300DLF	DIODE	△				
D751-754	1SR35200TB	DIODE	△			FILTER(S) AND OSCILLATOR(S)	
D755	MA165	DIODE					
D756	MA4068M	DIODE	△	CF201	RLFFETNGD01L	FILTER	
D901	1SS291TA	DIODE		CF202	RLFFETMGD01L	FILTER	
D903	MA4056MTA	DIODE	△	CF901	EFOEC6004T4	OSCILLATOR (6MHz)	
D904	MA165	DIODE		X101	RSXZ456KM07M	OSCILLATOR (456kHz)	
D906	MA165	DIODE	(E, EB, EP, G, GN)	X102	RLFDGTD01I	OSCILLATOR (10.65MHz)	
D907	MA165	DIODE		X103	SVQ49U722-S	OSCILLATOR (7.2MHz)	
D917	1SS291TA	DIODE					
D921	MA165	DIODE				DISPLAY TUBE (S)	
D922	MA4039MTA	DIODE	△				
D923	MA165	DIODE		FL901	RSL0155-F	DISPLAY TUBE	
D927, 928	MA165	DIODE					
D929	LN846RPH	L. E. D.				FM FRONT END PACK ASS'Y(S)	
D934	MA165	DIODE					
		VARIABLE RESISTOR(S)		Z120	ENV17290G1R	FM FRONT END	
						FUSE(S)	
VR471, 472	EVJYA1FA5C15	TONE CONTROL					
VR501	EUWMB025B15	VOLUME CONTROL		F1	XBA2C16TBO	FUSE, 125V, 1.6A	△
VR502	EVJ02QF02G15	BALANCE CONTROL		F2	XBA2C31TBO	FUSE, 25V, 3.15A	(G) △
		COIL (S)				SWITCH(ES)	
L101	ELESNR68MA	COIL	(E, EB, EP, G, GN)	S701	ESD26840A	VOLTAGE ADJUSTMENT	(G) △
L101	ELESNR0MA	COIL	(EG)	S946	EVQ21405R	NUMERIC 5	
L103	ELEXTR47MA9	COIL		S949	EVQ21405R	NUMERIC 4	
L105, 106	RLQZB822KT-D	COIL		S950	EVQ21405R	NUMERIC 6	
L151	SLM1B10M-1M	COIL		S952	EVQ21405R	NUMERIC 7	
L191	ELESNR68MA	COIL	(E, EB, EP, G, GN)	S954	EVQ21405R	CD	
L191	ELESNR56MA	COIL	(EG)	S955	EVQ21405R	TUNER	
L591, 592	RLQZPIROKT-Y	COIL		S957	EVQ21405R	NUMERIC 9	
L601, 602	RLQYR73M	COIL		S961	EVQ21405R	NUMERIC 8	
L701	SLQZ650MH49	COIL	(E, EB, EG, EP, GN) △	S962	EVQ21405R	NUMERIC 0	
L751	ELESNR101KA	COIL		S964	EVQ21405R	PHONO	
L901	RLQZP101KT-Y	COIL		S966	EVQ21405R	MEMORY	
		TRANSFORMER (S)		S967	EVQ21405R	MUTING	
				S970	EVQ21405R	TAPE/DCC	

Ref. No.	Part No.	Part Name & Description	Remarks	Ref. No.	Part No.	Part Name & Description	Remarks
S971	EVQ21405R	VCR2		JK791	SJSD16	AC INLET	(GN) △
S972	EVQ21405R	VCR1		JK793	SJS9231-1B	AC INLET	(G) △
S973	EVQ21405R	SP-B					
S974	EVQ21405R	FM MODE				GND PLATE (S)	
S975	EVQ21405R	BAND					
S976	EVQ21405R	DIRECT TUNING		E401	SNE1004-2	GND PLATE	
S977	EVQ21405R	TUNING DOWN		E601	SNE1004-2	GND PLATE	
S978	EVQ21405R	POWER					
S981	EVQ21405R	SP-A				FUSE HOLDER(S)	
S983	EVQ21405R	NUMERIC 3					
S984	EVQ21405R	NUMERIC 2		FC701, 702	EYF52BC	FUSE HOLDER	
S985	EVQ21405R	NUMERIC 1		FC703, 704	EYF52BC	FUSE HOLDER	(G)
S987	EVQ21405R	TUNING UP					
		RELAY(S)					
RL601, 602	RSY0013M-0	RELAY	△				
RL751	RSY0019M-0	RELAY	△				
		CONNECTOR(S) AND SOCKET(S)					
CN101, 102	RJU057W007	SOCKET (7P)					
CN301	RJS1A6603	CONNECTOR (3P)					
CN501	RJU003K010M1	SOCKET (10P)					
CN601	RJU057W004	SOCKET (4P)					
CN651	RJS1A6603	CONNECTOR (3P)					
CN701A	RJS1A6606	CONNECTOR (6P)					
CN701B	RJS1A6604	CONNECTOR (4P)					
CN701C	RJS1A6603	CONNECTOR (3P)					
CN710-716	RJS1A1101T1	CONNECTOR (1P)					
CN751	SJS305-1	CONNECTOR (3P)	(E, EB, EG, EP, GN)				
CN751	SJS702-1	CONNECTOR (7P)	(G)				
CN901-904	RJU003K008M1	SOCKET (8P)					
CP101, 102	RJT057W007-1	CONNECTOR (7P)					
CP501	RJT003K010-1	CONNECTOR (10P)					
CP601	RJT057W004-1	CONNECTOR (4P)					
CP901-904	RJT003K008-1	CONNECTOR (8P)					
		JACK(S) AND TERMINAL(S)					
HP601	RJJ63TS01	HEADPHONE JACK					
JK101	RJH4202M	ANT TERMINAL					
JK301	SJFK5-1	VCR2 IN TERMINAL					
JK302	SJFD7-6	VCR2 OUT TERMINAL					
JK401	SJF3069N	PHONO/CD TERMINAL					
JK402	SJF3069N	TAPE/VCR2/DCC TERMINAL					
JK403	SJF3069N	VCR1 TERMINAL					
JK406	RJJ33TR01	REMOTE CONTROL OUT TERMINAL					
JK601	RJR0054	SPEAKER (A) TERMINAL					
JK602	RJR0054	SPEAKER (B) TERMINAL					
JK651	RJS1A7402-1	FAN CONNECTOR					
JK791	SJS9236	AC INLET	(E, EB, EG, EP) △				

RESISTORS AND CAPACITORS

Notes : * Capacity values are in microfarads (μ F) unless specified otherwise, P=Pico-farads (pF) F=Farads (F)
 * Resistance values are in ohms, unless specified otherwise, 1K=1,000 (OHM), 1M=1,000k (OHM)

Ref. No.	Part No.	Values & Remarks	Ref. No.	Part No.	Values & Remarks	Ref. No.	Part No.	Values & Remarks
		RESISTORS			G, GN)	R615	ERDS2TJ184T	1/4W 180K
			R375, 376	ERDS2TJ102	1/4W 1K	R616	ERDS2TJ154	1/4W 150K
			R377, 378	ERDS2TJ223	1/4W 22K	R619	ERDS2TJ684	1/4W 680K
R103	ERDS2TJ101	1/4W 100	R401, 402	ERDS2TJ102	1/4W 1K	R620	ERDS2TJ473	1/4W 47K
R104	ERDS2TJ102	1/4W 1K	R405-408	ERDS2TJ102	1/4W 1K	R621, 622	ERD25FVJ180T	1/4W 18 Δ
R105	ERDS2TJ471	1/4W 470	R411-416	ERDS2TJ102	1/4W 1K	R623	ERDS2TJ684	1/4W 680K
R106	ERDS2TJ224T	1/4W 220K	R417, 418	ERDS2TJ473	1/4W 47K	R624	ERDS2TJ224T	1/4W 220K
R107	ERDS2TJ471	1/4W 470	R419-422	ERDS2TJ104	1/4W 100K	R625	ERD25FJ220	1/4W 22 Δ
R110	ERDS2TJ102	1/4W 1K	R423, 424	ERDS2TJ102	1/4W 1K	R626	ERDS2TJ473	1/4W 47K
R112	ERDS2TJ104	1/4W 100K	R425-427	ERDS2TJ103	1/4W 10K	R627-630	ERGISJ101E	1W 100
R113	ERDS2TJ103	1/4W 10K	R440	ERDS1FVJ820T	1/2W 82 Δ	R631, 632	ERDS2TJ223	1/4W 22K
R114	ERDS2TJ562	1/4W 5.6K	R441, 442	ERDS2TJ473	1/4W 47K	R633, 634	ERDS2TJ103	1/4W 10K
R115	ERDS2TJ561	1/4W 560	R443	ERDS2TJ330	1/4W 33	R635, 636	ERDS2TJ102	1/4W 1K
R116	ERDS2TJ102	1/4W 1K	R451, 452	ERDS2TJ224T	1/4W 220K	R637	ERDS2TJ472	1/4W 4.7K
R117	ERDS2TJ473	1/4W 47K	R453, 454	ERDS2TJ391	1/4W 390	R639, 640	ERDS2TJ474	1/4W 470K
R118	ERDS2TJ562	1/4W 5.6K	R455, 456	ERDS2TJ563	1/4W 56K	R641, 642	ERDS2TJ221	1/4W 220
R119	ERDS2TJ183T	1/4W 18K	R457, 458	ERDS2TJ271	1/4W 270	R643, 644	ERDS2TJ154	1/4W 150K
R120	ERDS2TJ473	1/4W 47K	R459, 460	ERDS2TJ680T	1/4W 68	R645	ERDS2TJ183T	1/4W 18K
R121	ERDS2TJ332	1/4W 3.3K	R461, 462	ERDS2TJ184T	1/4W 180K	R667, 668	ERGISJ121E	1W 120
R122	ERDS2TJ272T	1/4W 2.7K	R463, 464	ERDS2TJ123	1/4W 12K	R671-674	ERDS2TJ223	1/4W 22K
R124	ERDS2TJ271	1/4W 270	R465, 466	ERDS2TJ563	1/4W 56K	R675	ERDS2TJ682T	1/4W 6.8K
R125, 126	ERDS2TJ472	1/4W 4.7K	R467-470	ERDS2TJ102	1/4W 1K	R678	ERDS2TJ103	1/4W 10K
R127	ERDS2TJ103	1/4W 10K	R475, 476	ERDS2TJ471	1/4W 470	R679	ERDS2TJ222	1/4W 2.2K
R128	ERDS2TJ820	1/4W 82	R477-480	ERDS2TJ474	1/4W 470K	R680	ERDS2TJ473	1/4W 47K
R129	ERDS2TJ473	1/4W 47K	R481, 482	ERDS2TJ152	1/4W 1.5K	R681	ERDS2TJ332	1/4W 3.3K
R130, 131	ERDS2TJ102	1/4W 1K	R483, 484	ERDS2TJ392T	1/4W 3.9K	R682	ERDS1FVJ220T	1/2W 22 Δ
R132	ERDS2TJ103	1/4W 10K	R485, 486	ERDS2TJ223	1/4W 22K	R683	ERDS2TJ103	1/4W 10K
R133-137	ERDS2TJ102	1/4W 1K	R487, 488	ERDS2TJ392T	1/4W 3.9K	R684	ERDS2TJ153	1/4W 15K
R139, 140	ERDS2TJ272T	1/4W 2.7K	R489, 490	ERDS2TJ222	1/4W 2.2K	R685, 686	ERDS2TJ333	1/4W 33K
R141, 142	ERDS2TJ102	1/4W 1K	R491, 492	ERDS2TJ122	1/4W 1.2K	R687	ERDS2TJ103	1/4W 10K
R143, 144	ERDS2TJ222	1/4W 2.2K	R493, 494	ERDS2TJ333	1/4W 33K	R688	ERDS2TJ222	1/4W 2.2K
R145, 146	ERDS2TJ102	1/4W 1K (E, EB, EP, G, GN)	R501, 502	ERDS2TJ222	1/4W 2.2K	R689	ERDS2TJ270T	1/4W 27
R145, 146	ERDS2TJ561	1/4W 560 (EG)	R503, 504	ERDS2TJ103	1/4W 10K	R690	ERDS2TJ223	1/4W 22K
R147, 148	ERDS2TJ474	1/4W 470K	R509-512	ERDS2TJ332	1/4W 3.3K	R691	ERDS2TJ104	1/4W 100K
R149	ERDS2TJ680T	1/4W 68	R525, 526	ERDS2TJ102	1/4W 1K	R692	ERDS2TJ103	1/4W 10K
R171, 172	ERDS2TJ102	1/4W 1K	R528	ERDS2TJ822	1/4W 8.2K	R693	ERDS2TJ223	1/4W 22K
R173	ERDS2TJ471	1/4W 470	R529	ERDS2TJ824	1/4W 820K	R694	ERDS2TJ335T	1/4W 3.3M
R175	ERDS2TJ102	1/4W 1K	R532-534	ERDS2TJ102	1/4W 1K	R705	ERDS1FVJ6R8T	1/2W 6.8 Δ
R176	ERDS2TJ391	1/4W 390	R537	ERDS2TJ102	1/4W 1K	R707	ERDS2TJ332	1/4W 3.3K
R191	ERDS2TJ103	1/4W 10K (E, EB, EP, G, GN)	R538	ERDS2TJ472	1/4W 4.7K	R708	ERDS2TJ102	1/4W 1K
R192	ERDS2TJ122	1/4W 1.2K (E, EB, EP, G, GN)	R547, 548	ERGISJ820E	1W 82	R711	ERD25FVJ221T	1/4W 220 Δ
R193	ERDS2TJ182	1/4W 1.8K (E, EB, EP, G, GN)	R591	ERDS1FVJ2R2T	1/2W 2.2 Δ	R714	ERDS2TJ472	1/4W 4.7K
R194	ERDS2TJ122	1/4W 1.2K (E, EB, EP, G, GN)	R601, 602	ERDS2TJ221	1/4W 220	R715, 716	ERDS2TJ1R5T	1/4W 1.5
R195	ERDS2TJ222	1/4W 2.2K (E, EB, EP, G, GN)	R603, 604	ERDS2TJ563	1/4W 56K	R717	ERDS2TJ752T	1/4W 7.5K
			R605, 606	ERDS2TJ182	1/4W 1.8K	R718	ERDS2TJ682T	1/4W 6.8K
			R607, 608	ERDS2TJ563	1/4W 56K	R719	ERDS1FVJ220T	1/2W 22 Δ
			R609, 610	ERDS2TJ100	1/4W 10	R721	ERDS2TJ182	1/4W 1.8K
			R611, 612	ERDS1FVJ100T	1/2W 10 Δ	R723	ERD25FVJ4R7T	1/4W 4.7 Δ
			R613, 614	ERDS2TJ102	1/4W 1K	R724	ERDS2TJ122	1/4W 1.2K (E, EB, EG,

Ref. No.	Part No.	Values & Remarks	Ref. No.	Part No.	Values & Remarks	Ref. No.	Part No.	Values & Remarks
		EP)	R984	ERDS2TJ222	1/4W 2. 2K	C173	ECEA1CKA220B	16V 22U
R724	ERDS2TJ222	1/4W 2. 2K (G, GN)	R985	ERDS2TJ332	1/4W 3. 3K	C174	ECEA1CKA101B	16V 100U
R727	ERD25FVJ180T	1/4W 18 Δ	R986	ERDS2TJ472	1/4W 4. 7K	C175, 176	ECBT1C103NS5	16V 0. 01U
R728	ERDS1FVJ100T	1/2W 10 Δ	R987	ERDS2TJ682T	1/4W 6. 8K	C181	ECBT1H471KB5	50V 470P
R729	ERDS2TJ332	1/4W 3. 3K	R991	ERDS2TJ103	1/4W 10K	C196	ECBT1H102KB5	50V 1000P
R754	ERDS2TJ102	1/4W 1K	R1201-1205	ERDS2TJ102	1/4W 1K	C375, 376	ECBT1H221KB5	50V 220P
R901	ERDS2TJ102	1/4W 1K	R1209-1212	ERDS2TJ102	1/4W 1K	C377, 378	ECBT1H821KB5	50V 820P
R902	ERDS2TJ681	1/4W 680	R1214	ERDS2TJ102	1/4W 1K	C401	ECEA1VKA4R7B	35V 4. 7U
R903, 904	ERDS2TJ104	1/4W 100K				C402, 403	ECBT1E103ZF	25V 0. 01U
R905, 906	ERDS2TJ103	1/4W 10K			CAPACITORS	C404	ECEA1VKA4R7B	35V 4. 7U
R907-911	ERDS2TJ104	1/4W 100K				C405	ECBT1H101KB5	50V 100P
R912	ERDS2TJ102	1/4W 1K	C101	ECBT1C103NS5	16V 0. 01U	C406	ECBT1H102KB5	50V 1000P
R913, 914	ERDS2TJ104	1/4W 100K	C103	ECBT1C103NS5	16V 0. 01U	C409, 410	ECEA1CKA220B	16V 22U
R920	ERDS2TJ271	1/4W 270	C104	ECBT1H102KB5	50V 1000P	C411, 412	ECBT1H101KB5	50V 100P
R921	ERDS2EJ121	1/4W 120	C105	ECBT1H470J5	50V 47P	C413, 414	ECEA1CKA100B	16V 10U
R922	ERDS2TJ472	1/4W 4. 7K	C106	ECBT1C103NS5	16V 0. 01U	C415, 416	ECBT1E103ZF	25V 0. 01U
R923	ERDS2TJ102	1/4W 1K	C107	ECBT1H473ZF5	50V 0. 047U	C417, 418	ECBT1H101KB5	50V 100P
R926	ERDS2TJ122	1/4W 1. 2K	C108	ECBT1H100JC5	50V 10P (E, EB, EP, G, GN)	C419-422	ECBT1H331KB5	50V 330P
R927	ERDS2TJ181T	1/4W 180				C425, 426	ECBT1H101KB5	50V 100P
R928	ERDS2TJ222	1/4W 2. 2K	C108	ECBT1H8R2KC5	50V 8. 2P (EG)	C427, 428	ECBT1H221KB5	50V 220P
R929	ERDS2TJ562	1/4W 5. 6K	C109, 110	ECBT1C103NS5	16V 0. 01U	C431, 432	ECEA1CKA100B	16V 10U
R930, 931	ERDS2TJ101	1/4W 100	C111	ECEA1EKA4R7B	25V 4. 7U	C440	ECBT1E103ZF	25V 0. 01U
R946-949	ERDS2TJ103	1/4W 10K	C112	ECBT1C103NS5	16V 0. 01U	C451, 452	ECEA1VKA4R7B	35V 4. 7U
R950	ERDS2TJ102	1/4W 1K	C113	ECBT1H102KB5	50V 1000P	C453, 454	ECBT1H100JC5	50V 10P
R951	ERDS2TJ122	1/4W 1. 2K	C114	ECEA1HKA3R3B	50V 3. 3U	C455, 456	ECBT1H102KB5	50V 1000P
R952	ERDS2TJ152	1/4W 1. 5K	C115	ECEA1EKA4R7B	25V 4. 7U	C457, 458	ECEA1AKA330B	10V 33U
R953	ERDS2TJ182	1/4W 1. 8K	C116	ECBT1C822MS5	16V 8200P	C459, 460	ECFR1E223KR	25V 0. 022U
R954	ERDS2TJ222	1/4W 2. 2K	C117	ECQB1H471JF3	50V 470P	C461, 462	ECFR1E682KR	25V 6800P
R955	ERDS2TJ332	1/4W 3. 3K	C118, 119	ECQB1H103JF3	50V 0. 01U	C463, 464	ECEA1VKA4R7B	35V 4. 7U
R956	ERDS2TJ472	1/4W 4. 7K	C120, 121	ECEA1HKA010B	50V 1U	C465, 466	ECBT1E103ZF	25V 0. 01U
R957	ERDS2TJ682T	1/4W 6. 8K	C122	ECEA1HKA2R2B	50V 2. 2U	C469, 470	ECBT1H181KB5	50V 180P
R960	ERDS2TJ102	1/4W 1K	C123	ECEA1HKA010B	50V 1U	C471, 472	ECEA1HKA3R3B	50V 3. 3U
R961	ERDS2TJ122	1/4W 1. 2K	C124	ECBT1H102KB5	50V 1000P	C475, 476	ECBT1H150J5	50V 15P
R962	ERDS2TJ152	1/4W 1. 5K	C125	ECBT1H150JC5	50V 15P	C477, 478	ECBT1H221KB5	50V 220P
R963	ERDS2TJ182	1/4W 1. 8K	C126	ECBT1H1042F5	50V 0. 1U	C479, 480	ECBT1H560J5	50V 56P
R964	ERDS2TJ222	1/4W 2. 2K	C127	ECEA1CKA220B	16V 22U	C481-484	ECEA1VKA4R7B	35V 4. 7U
R965	ERDS2TJ332	1/4W 3. 3K	C128	ECBT1C103NS5	16V 0. 01U	C485, 486	ECFR1E123KR	25V 0. 012U
R966	ERDS2TJ472	1/4W 4. 7K	C129, 130	ECEA0JKA101B	6. 3V 100U	C487, 488	ECQV1H683JM3	50V 0. 068U
R967	ERDS2TJ682T	1/4W 6. 8K	C131	ECBT1C103NS5	16V 0. 01U	C489, 490	ECBT1C562KR5	16V 5600P
R970	ERDS2TJ102	1/4W 1K	C132	ECBT1H102KB5	50V 1000P	C491, 492	ECFR1E273KR	25V 0. 027U
R971	ERDS2TJ122	1/4W 1. 2K	C133	ECBT1H150JC5	50V 15P	C495, 496	ECBT1E103ZF	25V 0. 01U
R972	ERDS2TJ152	1/4W 1. 5K	C134	ECBT1H180JC5	50V 18P	C503, 504	ECEA1VKA4R7B	35V 4. 7U
R973	ERDS2TJ182	1/4W 1. 8K	C135, 136	ECBT1C103KS5	16V 0. 01U	C518	ECEA1HKN010B	50V 1U
R974	ERDS2TJ222	1/4W 2. 2K	C137, 138	ECBT1H561KB5	50V 560P	C541, 542	ECEA1HN100SB	50V 10U
R975	ERDS2TJ332	1/4W 3. 3K	C139, 140	ECQB1H682JF3	50V 6800P	C543, 544	ECBT1C332KR5	16V 3300P
R976	ERDS2TJ472	1/4W 4. 7K	C141-144	ECEA1HKA010B	50V 1U	C591, 592	ECEA0JKA101B	6. 3V 100U
R977	ERDS2TJ682T	1/4W 6. 8K	C145	ECBT1H220JC5	50V 22P	C593, 594	ECFR1E104KR	25V 0. 1U
R978	ERDS2TJ123	1/4W 12K	C146	ECBT1H331KB5	50V 330P	C595	ECBT1E103ZF	25V 0. 01U
R980	ERDS2TJ102	1/4W 1K	C147	ECBT1H102KB5	50V 1000P	C601, 602	ECEA1EKN2R2B	25V 2. 2U
R981	ERDS2TJ122	1/4W 1. 2K	C148, 149	ECBT1C103NS5	16V 0. 01U	C603, 604	ECBT1H561KB5	50V 560P
R982	ERDS2TJ152	1/4W 1. 5K	C150	ECBT1H1042F5	50V 0. 1U	C605, 606	ECA1JM330B	63V 33U
R983	ERDS2TJ182	1/4W 1. 8K	C172	ECBT1H331KB5	50V 330P	C607, 608	ECRR1H100K5	50V 10P

Ref.No.	Part No.	Values & Remarks	Ref.No.	Part No.	Values & Remarks			
C609, 610	ECBT1H151KB5	50V 150P	C913, 914	ECEA1VKA100B	35V 10U			
C611, 612	ECQV1H473JM3	50V 0.047U	C916	ECEA1HKA010B	50V 1U			
C613, 614	ECBA1H681KB5	50V 680P	C920	ECEA1HKA010B	50V 1U			
C615	ECEA2AN2R2SB	100V 2.2U	C921-928	ECBT1H331KB5	50V 330P			
C616	ECEA2AU100	100V 10U	C929-932	ECBT1H101KB5	50V 100P			
C617	ECA1HM470B	50V 47U						
C618	ECEA2AU100	100V 10U						
C621	ECEA2AU100	100V 10U						
C623-626	ECKT1H223ZF	50V 0.022U						
C627	ECKR2H101KB5	500V 100P						
C628	ECBT1H101KB5	50V 100P						
C629	ECBT1E223ZF	25V 0.022U						
C651	ECEA1HKA2R2B	50V 2.2U						
C652	ECEA1CKA100B	16V 10U						
C653	ECBT1E223ZF	25V 0.022U						
C655	RCE0JKA221BV	6.3V 220U						
C701	ECBT1E103ZF	25V 0.01U						
C702	ECQE2104KF3	250V 0.1U						
C703, 704	ECES56V472NX	56V 4700U (E, EB, EG, EP) Δ						
C703, 704	ECES75V752UX	75V 7500U (G, GN) Δ						
C705, 706	ECA1VM472B	50V 4700U (E, EB, EG, EP) Δ						
C705, 706	ECA1HM222B	50V 2200U (G, GN) Δ						
C707	RCE1VM101BV	35V 100P						
C708	ECKR1H103ZF5	50V 0.01U						
C709	ECEA1CKA330B	16V 33U						
C710	ECBT1E103ZF	25V 0.01U						
C711	ECKR1H103ZF5	50V 0.01U						
C712	ECA1HM470B	50V 47U						
C713	ECKR1H103ZF5	50V 0.01U						
C716	ECEA2AU100	100V 10U						
C720	ECEA1EKA220B	25V 22U						
C722	ECQE2104KF3	250V 0.1U						
C751	ECKWNS102MBM	400V 1000P Δ						
C752	ECKR1H103ZF5	50V 0.01U						
C753	ECA1EM102B	25V 1000U Δ						
C754	ECBT1E103ZF	25V 0.01U						
C756	ECBT1E103ZF	25V 0.01U						
C757	ECEA1CKA470B	16V 47U						
C758	ECEA1AKA101B	10V 100U						
C759	ECEA1EKA220B	25V 22U						
C891	ECFR1E392KR	25V 3900P						
C901	ECA0JM102B	6.3V 1000U						
C902	ECBTOJ223MS5	6.3V 0.022U (E, EB, EG, EP)						
C902	ECBT1E103ZF	25V 0.01U (G, GN)						
C903	ECBT1E103ZF	25V 0.01U						
C904	ECA0JM471B	6.3V 470U						
C906	ECEA0JKA101B	6.3V 100U						
C908, 909	ECBT1E103ZF	25V 0.01U						
C911, 912	ECEA2AU100	100V 10U						

REPLACEMENT PARTS LIST

Notes: *Important safety notice:

Components identified by Δ mark have special characteristics important for safety. Furthermore, special parts which have purposes of fire-retardant (resistors), high-quality sound (capacitors), low-noise (resistors), etc. are used. When replacing any of components, be sure to use only manufacturer's specified parts shown in the parts list.
 *The parenthesized indications in the Remarks columns specify the areas. (Refer to the cover page for area.)
 Parts without these indications can be used for all areas.
 *Remote Control Ass'y: Supply period for three years from termination of production.
 *The "(SF)" mark denotes the standard part.

Ref. No.	Part No.	Part Name & Description	Remarks	Ref. No.	Part No.	Part Name & Description	Remarks
		PACKING MATERIAL		A1	RQF2297	INSTRUCTION MANUAL ASS'Y	(EP)
				A2	RJA0019-2K	AC POWER SUPPLY CORD	(E, EG, EP, G) Δ (SF)
				A2	VJA0733	AC POWER SUPPLY CORD	(EB) Δ (SF)
				A2	RJA0036-K	AC POWER SUPPLY CORD	(GN) Δ (SF)
P1	RPG2062	PACKING CASE	(E, EG, EP, G, GN)	A3	RSA0007	FM INDOOR ANTENNA	
P1	RPG2063	PACKING CASE	(EB)	A4	RSA0010	AM LOOP ANTENNA SET	
P2	RPN0752	CUSHION		A4-1	RMN0244	AM ANTENNA HOLDER	
P3	RPQ0164	PAD (ACCESSORIES)		A4-2	XTN3+10AFZ	SCREW	
P4	XZB24K34C04	PROTECTION BAG (ACCESSORIES)		A5	RQCB0169	SERVICENTER LIST	(E, EB, EG, G, GN)
P5	XZB60X65A01Z	PROTECTION BAG (UNIT)		A6	RQA0013	WARRANTY CARD	(E, EB, EG)
P6	RPH0032	PROTECTION SHEET	(EB, GN)	A6	RQX7433ZA	WARRANTY CARD	(GN)
		ACCESSORIES		A7	RAK-SA113XH	REMOTE CONTROL TRANSMITTER	
				A7-1	RKK0057-K	BATTERY COVER	FOR R/C TRANSMITTER
A1	RFKSAGX170E	INSTRUCTION MANUAL ASS'Y	(E)	A8	SJP9009	ATTACHMENT PLUG	(EB) Δ
A1	RFKSAGX170G	INSTRUCTION MANUAL ASS'Y	(G)	A9	RFE0014	ANTENNA PLUG	(G, GN)
A1	RQT2458-B	INSTRUCTION MANUAL	(EB, GN)	A10	RQLA0134	VOLTAGE CAUTION LABEL	(G)
A1	RQT2456-D	INSTRUCTION MANUAL	(EG)	A11	SJP5213-1	POWER PLUG ADAPTOR	(G) Δ

PACKAGING

