



## **Instructions**

**Tektronix**

**A605**  
**500 Amp AC Current Probe**  
**070-8880-00**



Copyright© Tektronix, Inc., 1993. All rights reserved.

Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supercedes that in all previously published material. Specifications and price change priviledges reserved.

Printed in the U.S.A.

Tektronix, Inc., P.O. Box 1000, Wilsonville, OR 97070

TEKTRONIX,TEK are registered trademarks of Tektronix, Inc.



## WARRANTY

Tektronix warrants that this product will be free from defects in materials and workmanship for a period of one (1) year from the date of shipment. If any such product proves defective during this warranty period, Tektronix, at its option, either will repair the defective product without charge for parts and labor, or will provide a replacement in exchange for the defective product.

In order to obtain service under this warranty, Customer must notify Tektronix of the defect before the expiration of the warranty period and make suitable arrangements for the performance of service. Customer shall be responsible for packaging and shipping the defective product to the service center designated by Tektronix, with shipping charges prepaid. Tektronix shall pay for the return of the product to Customer if the shipment is to a location within the country in which the Tektronix service center is located. Customer shall be responsible for paying all shipping charges, duties, taxes, and any other charges for products returned to any other locations.

This warranty shall not apply to any defect, failure or damage caused by improper use or improper or inadequate maintenance and care. Tektronix shall not be obligated to furnish service under this warranty a) to repair damage resulting from attempts by personnel other than Tektronix representatives to install, repair or service the product; b) to repair damage resulting from improper use or connection to incompatible equipment; or c) to service a product that has been modified or integrated with other products when the effect of such modification or integration increases the time or difficulty of servicing the product.

**THIS WARRANTY IS GIVEN BY TEKTRONIX WITH RESPECT TO THIS PRODUCT IN LIEU OF ANY OTHER WARRANTIES, EXPRESSED OR IMPLIED. TEKTRONIX AND ITS VENDORS DISCLAIM ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. TEKTRONIX' RESPONSIBILITY TO REPAIR OR REPLACE DEFECTIVE PRODUCTS IS THE SOLE AND EXCLUSIVE REMEDY PROVIDED TO THE CUSTOMER FOR BREACH OF THIS WARRANTY. TEKTRONIX AND ITS VENDORS WILL NOT BE LIABLE FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES IRRESPECTIVE OF WHETHER TEKTRONIX OR THE VENDOR HAS ADVANCE NOTICE OF THE POSSIBILITY OF SUCH DAMAGES.**



## Product Description

The A605 is designed to extend the AC current range of a multimeter up to 500 amps by acting as a proportional current/voltage transformer. It is compatible with multimeters having an AC volts function with an input resistance  $\geq 1 \text{ M}\Omega$ .

## General Safety Summary

### Observe Maximum Working Voltage

Do not use the A605 above 440 VAC.

### Do Not Operate in Wet/Damp Conditions

To avoid personal injury or damage to this product from electric shock, do not operate this product in wet/damp conditions.

### Do Not Operate in an Explosive Atmosphere

To avoid personal injury or fire hazard, do not operate this product in an explosive atmosphere.

### Do Not Immerse in Liquids

Clean the probe using a damp cloth. Refer to the cleaning instructions on page 6.

### Do Not Use if Damaged

If you suspect that there is damage to this product, have it inspected by qualified service personnel.



## Operating Basics



**WARNING.** Do not clamp the probe onto circuits with voltages greater than 440 VAC. Personal injury or damage to the probe may result.

Always connect the probe to the instrument before clamping onto the circuit under test.

1. Connect the black lead to the meter **COM**, and the red lead to the **V $\Omega$**  input. Set the meter to the AC Volts position. See Figure 1 for connection to a Tektronix DM 254.





Figure 1: Meter Connections

2. Connect the probe to the circuit by opening the jaws and clamping around the conductor. *Grabbing both the “hot” and neutral wires may give you a zero reading.* See Figure 2.




**Figure 2: Connecting the A605**

3. Adjust the meter as necessary to get a useable reading.

Each millivolt displayed on the meter indicates an ampere of current in the circuit. For example: an 80 mV reading = 80 Amps in the circuit.

(Remember to unclamp the probe from the conductor before disconnecting it from your meter or instrument.)

To increase the measurement sensitivity of the A605, loop additional turns of the wire under test through the jaws. See Figure 3. The sensitivity of the A605 will be multiplied by the number of loops in the jaws. For example:  $1 \text{ mV/A} \times 4 \text{ turns} = 4 \text{ mV/A}$ .




**Figure 3: Increasing the A605 Sensitivity**



## Functional Check

Follow the function check procedure to determine if your probe is working properly.

### AC Current



**Figure 4: Basic AC Test Circuit**

To check your current probe, you will need a known AC voltage and resistance. For example, measured 60 Hz line voltage and an incandescent lamp of known approximate wattage are adequate. See Figure 4. *The power consumption of the lamp is usually printed on the lamp. The lamp used should be designed for the test voltage.*

1. Connect the probe to the instrument.
2. Connect the lamp to the line voltage.
3. Measure the line voltage at the lamp.



## Functional Check

---

4. Clamp the probe around one of the wires and measure the current. (Additional loops may be necessary to get a reasonable reading. See the *Operating Basics* section.)
5. Use the provided formulas to calculate current and error.

$$Current_{calculated} = \frac{Power_{known}}{Voltage_{measured}}$$

$$\% Error = \left[ 1 - \frac{Current_{measured}}{Current_{calculated}} \right] \times 100$$

For example: given measured line voltage of 115 VAC, a 60 watt light bulb, and 510 mA of measured current, find the calculated current.

$$\frac{60 \text{ watts}}{115 \text{ VAC}} = 522 \text{ mA}_{calculated}$$

$$\left[ 1 - \frac{510 \text{ mA}_{measured}}{522 \text{ mA}_{calculated}} \right] \times 100 = 2.3\% Error$$

An error of  $\pm 10\%$  is acceptable, and a good indication that the probe and meter are functioning properly.

The linearity of the probe can be checked by the method used to increase measurement sensitivity. By increasing the number of loops in the jaws, the measured current should increase proportionately.





## Maintenance

### Cleaning

To clean the probe body, use a soft cloth dampened in a solution of mild detergent and water. To clean the core, open the jaw and clean the exposed core surfaces with a cotton swab dampened with isopropyl alcohol (isopropanol) or ethyl alcohol (fotocol or ethanol). Lubricate the jaws mating surfaces with a light oil.

Do not use chemicals containing benzine, benzene, toluene, xylene, acetone, or similar solvents.

Do not immerse the probe in liquids or use abrasive cleaners.

### Preparation for Shipment

If the original packaging is unfit for use or not available, use the following packaging guidelines:

1. Use a corrugated cardboard shipping carton having inside dimensions at least one inch greater than the probe dimensions. The box should have a carton test strength of at least 200 pounds.
2. Put the probe into a plastic bag or wrap to protect it from dampness.
3. Place the probe into the box and stabilize it with light packing material.
4. Seal the carton with shipping tape.

## Specifications

These characteristics apply to a A605 probe installed on a Tektronix DM254 multimeter in an environment within the limits described in Table 3. For best results, a true RMS multimeter should be used.

**Table 1: Electrical Characteristics**

Output	1 mV/A
Accuracy	$\pm 2.5\%$ from 4 to 500 A, $\pm 0.6$ A (48 to 440 Hz) $\pm 3.5\%$ from 4 to 500 A, $\pm 0.6$ A (440 to 1000 Hz)
Maximum Working Current	500 A <sub>PEAK</sub>
Maximum Working Voltage	440 V <sub>RMS</sub> (650 VDC + AC <sub>PEAK</sub> )
Frequency Range	48 Hz to 1 kHz

**Table 2: Physical Characteristics**

Dimensions	195 mm x 66 mm x 34 mm (7.68 x 2.60 x 1.34 inches)
Maximum Conductor Size	30 mm (1.18 inches)
Cable Length	1.5 m (5 feet)
Weight	350 g (12 oz)



---

Specifications

---

**Table 3: Environmental Characteristics**

---

Temperature	
Working	0°C to +50°C (+32° to +122°F)
Storage	-20°C to +80°C (-4° to +176°F)
Humidity	0° C to 40° C, 95% humidity 40° C to 50° C, 45% humidity

---

A horizontal decorative bar with a dark gray background and a white diagonal slash on the left side.

## Replaceable Parts

The A605 is shipped with the following item(s):

- these instructions  
Tektronix part number 070-8880-00

The A605 does not have any user repairable assemblies. If you should have trouble with your probe, contact you local Tektronix Service Center or representative for help.

For other needs or questions, please call this toll-free number:

1-800-TEK-WIDE, extension 2400  
(1-800-835-9433, extension 2400)

If you are outside North America, please contact the Tektronix office or distributor nearest you.