

# User Manual

**Tektronix**

**WCA230A & WCA280A Option 25  
cdma2000 Analysis Software**

**071-1367-00**

This document supports software version 1.00 and above.

**[www.tektronix.com](http://www.tektronix.com)**

Copyright © Tektronix, Inc. All rights reserved.

Tektronix products are covered by U.S. and foreign patents, issued and pending. Information in this publication supercedes that in all previously published material. Specifications and price change privileges reserved.

Tektronix, Inc., P.O. Box 500, Beaverton, OR 97077

TEKTRONIX and TEK are registered trademarks of Tektronix, Inc.

## **Software Warranty**

Tektronix warrants that the media on which this software product is furnished and the encoding of the programs on the media will be free from defects in materials and workmanship for a period of three (3) months from the date of shipment. If a medium or encoding proves defective during the warranty period, Tektronix will provide a replacement in exchange for the defective medium. Except as to the media on which this software product is furnished, this software product is provided "as is" without warranty of any kind, either express or implied. Tektronix does not warrant that the functions contained in this software product will meet Customer's requirements or that the operation of the programs will be uninterrupted or error-free.

In order to obtain service under this warranty, Customer must notify Tektronix of the defect before the expiration of the warranty period. If Tektronix is unable to provide a replacement that is free from defects in materials and workmanship within a reasonable time thereafter, Customer may terminate the license for this software product and return this software product and any associated materials for credit or refund.

**THIS WARRANTY IS GIVEN BY TEKTRONIX IN LIEU OF ANY OTHER WARRANTIES, EXPRESS OR IMPLIED. TEKTRONIX AND ITS VENDORS DISCLAIM ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. TEKTRONIX' RESPONSIBILITY TO REPLACE DEFECTIVE MEDIA OR REFUND CUSTOMER'S PAYMENT IS THE SOLE AND EXCLUSIVE REMEDY PROVIDED TO THE CUSTOMER FOR BREACH OF THIS WARRANTY. TEKTRONIX AND ITS VENDORS WILL NOT BE LIABLE FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES IRRESPECTIVE OF WHETHER TEKTRONIX OR THE VENDOR HAS ADVANCE NOTICE OF THE POSSIBILITY OF SUCH DAMAGES.**

## **Hardware Warranty**

Tektronix warrants that the products that it manufactures and sells will be free from defects in materials and workmanship for a period of one (1) year from the date of shipment. If a product proves defective during this warranty period, Tektronix, at its option, either will repair the defective product without charge for parts and labor, or will provide a replacement in exchange for the defective product.

In order to obtain service under this warranty, Customer must notify Tektronix of the defect before the expiration of the warranty period and make suitable arrangements for the performance of service. Customer shall be responsible for packaging and shipping the defective product to the service center designated by Tektronix, with shipping charges prepaid. Tektronix shall pay for the return of the product to Customer if the shipment is to a location within the country in which the Tektronix service center is located. Customer shall be responsible for paying all shipping charges, duties, taxes, and any other charges for products returned to any other locations.

This warranty shall not apply to any defect, failure or damage caused by improper use or improper or inadequate maintenance and care. Tektronix shall not be obligated to furnish service under this warranty a) to repair damage resulting from attempts by personnel other than Tektronix representatives to install, repair or service the product; b) to repair damage resulting from improper use or connection to incompatible equipment; c) to repair any damage or malfunction caused by the use of non-Tektronix supplies; or d) to service a product that has been modified or integrated with other products when the effect of such modification or integration increases the time or difficulty of servicing the product.

**THIS WARRANTY IS GIVEN BY TEKTRONIX IN LIEU OF ANY OTHER WARRANTIES, EXPRESS OR IMPLIED. TEKTRONIX AND ITS VENDORS DISCLAIM ANY IMPLIED WARRANTIES OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. TEKTRONIX' RESPONSIBILITY TO REPAIR OR REPLACE DEFECTIVE PRODUCTS IS THE SOLE AND EXCLUSIVE REMEDY PROVIDED TO THE CUSTOMER FOR BREACH OF THIS WARRANTY. TEKTRONIX AND ITS VENDORS WILL NOT BE LIABLE FOR ANY INDIRECT, SPECIAL, INCIDENTAL, OR CONSEQUENTIAL DAMAGES IRRESPECTIVE OF WHETHER TEKTRONIX OR THE VENDOR HAS ADVANCE NOTICE OF THE POSSIBILITY OF SUCH DAMAGES.**

# Table of Contents

<b>Preface .....</b>	<b>vii</b>
About This Manual .....	vii
Related Manuals.....	vii
Contacting Tektronix .....	viii

## Getting Started

<b>Getting Started .....</b>	<b>1-1</b>
Product Description .....	1-1

## Operating Basics

<b>Functional Overview .....</b>	<b>2-1</b>
<b>cdma2000 Forward Link Measurements .....</b>	<b>2-3</b>
Modulation Accuracy Measurement .....	2-4
Code Domain Power Measurement .....	2-12
Channel Power Measurement .....	2-21
OBW Measurement .....	2-22
ACPR Measurement .....	2-23
Spectrum Emission Mask Measurement .....	2-24
Intermodulation Measurement .....	2-26
CCDF Measurement .....	2-27
Pilot to Code Channel Measurement .....	2-30
<b>cdma2000 Reverse Link Measurements .....</b>	<b>2-33</b>
Modulation Accuracy Measurement .....	2-34
Code Domain Power Measurement .....	2-42
Pilot to Code Channel Measurement .....	2-45
Gated Output Power Measurement .....	2-49
<b>Editing the Measurement Limits .....</b>	<b>2-51</b>
Using the Measurement Limits Editor .....	2-51
Saving and Loading Measurement Limits .....	2-60
Measurement Limit Defaults .....	2-61

## Syntax and Commands

<b>Command Groups .....</b>	<b>3-1</b>
<b>:CONFigure Commands .....</b>	<b>3-11</b>
<b>:DISPlay Commands .....</b>	<b>3-17</b>
<b>:FETCh Commands .....</b>	<b>3-43</b>
<b>:MMEMory Commands .....</b>	<b>3-61</b>
<b>:READ Commands .....</b>	<b>3-63</b>
<b>:SENSe Commands .....</b>	<b>3-75</b>

## Appendices

<b>Appendix A: Specifications .....</b>	<b>A-1</b>
<b>Appendix B: Factory Default Settings .....</b>	<b>B-1</b>
<b>Appendix C: Setting Range .....</b>	<b>C-1</b>
<b>Appendix D: SCPI Conformance Information .....</b>	<b>D-1</b>

## Index

# List of Figures

<b>Figure 2-1: Menu diagram showing measurement functions available in Option 25 .....</b>	<b>2-1</b>
<b>Figure 2-2: Modulation accuracy measurement .....</b>	<b>2-4</b>
<b>Figure 2-3: Modulation accuracy display .....</b>	<b>2-7</b>
<b>Figure 2-4: EVM display .....</b>	<b>2-8</b>
<b>Figure 2-5: MagErr display .....</b>	<b>2-9</b>
<b>Figure 2-6: PhaseErr display .....</b>	<b>2-10</b>
<b>Figure 2-7: Symbol table display .....</b>	<b>2-11</b>
<b>Figure 2-8: Code domain power measurement .....</b>	<b>2-12</b>
<b>Figure 2-9: Code domain power display .....</b>	<b>2-15</b>
<b>Figure 2-10: Power codogram display .....</b>	<b>2-17</b>
<b>Figure 2-11: IQ power graph display .....</b>	<b>2-19</b>
<b>Figure 2-12: Channel power measurement .....</b>	<b>2-21</b>
<b>Figure 2-13: OBW measurement .....</b>	<b>2-22</b>
<b>Figure 2-14: ACPR measurement .....</b>	<b>2-23</b>
<b>Figure 2-15: Spectrum emission mask measurement .....</b>	<b>2-24</b>
<b>Figure 2-16: Intermodulation measurement .....</b>	<b>2-26</b>
<b>Figure 2-17: CCDF measurement (single view) .....</b>	<b>2-27</b>
<b>Figure 2-18: Scale settings in the CCDF display .....</b>	<b>2-29</b>
<b>Figure 2-19: Pilot to code channel measurement .....</b>	<b>2-30</b>
<b>Figure 2-20: Modulation accuracy measurement-reverse link .....</b>	<b>2-34</b>
<b>Figure 2-21: Modulation accuracy display-reverse link .....</b>	<b>2-37</b>
<b>Figure 2-22: EVM display-reverse link .....</b>	<b>2-38</b>
<b>Figure 2-23: MagErr display-reverse link .....</b>	<b>2-39</b>
<b>Figure 2-24: PhaseErr display-reverse link .....</b>	<b>2-40</b>
<b>Figure 2-25: Symbol table display-reverse link .....</b>	<b>2-41</b>
<b>Figure 2-26: Code domain power measurement-reverse link .....</b>	<b>2-42</b>
<b>Figure 2-27: Pilot to code channel measurement-reverse link .....</b>	<b>2-45</b>
<b>Figure 2-28: Gated output power measurement .....</b>	<b>2-49</b>
<b>Figure 2-29: Measurement limits editor .....</b>	<b>2-51</b>
<b>Figure 2-30: ACPR measurement limits editor .....</b>	<b>2-54</b>
<b>Figure 2-31: Spectrum emission mask measurement limits editor .....</b>	<b>2-56</b>
<b>Figure 2-32: Gated output power measurement limits editor .....</b>	<b>2-58</b>

## List of Figures

---

# List of Tables

<b>Table 2-1: Measurement limits items .....</b>	<b>2-52</b>
<b>Table 2-2: Measurement limit items for the ACPR measurement .....</b>	<b>2-54</b>
<b>Table 2-3: Measurement limit items for the spectrum emission mask measurement .....</b>	<b>2-56</b>
<b>Table 2-4: Measurement limit items for the gated output power measurement .....</b>	<b>2-58</b>
<b>Table 2-5: Forward link common limits .....</b>	<b>2-61</b>
<b>Table 2-6: Reverse link common limits .....</b>	<b>2-61</b>
<b>Table 2-7: Forward link: all band classes .....</b>	<b>2-62</b>
<b>Table 2-8: Reverse link: all band classes .....</b>	<b>2-62</b>
<b>Table 2-9: Forward link: BC (band class) 0, 2, 3, 5, and 9 .....</b>	<b>2-63</b>
<b>Table 2-10: Forward link: BC (band class) 1, 4, and 8 .....</b>	<b>2-63</b>
<b>Table 2-11: Forward link: BC (band class) 3b .....</b>	<b>2-64</b>
<b>Table 2-12: Forward link: BC (band class) 6 .....</b>	<b>2-64</b>
<b>Table 2-13: Forward link: BC (band class) 7 .....</b>	<b>2-65</b>
<b>Table 2-14: Reverse link: BC (band class) 0, 2, 3, 5, and 9 .....</b>	<b>2-65</b>
<b>Table 2-15: Reverse link: BC (band class) 1, 4, and 8 .....</b>	<b>2-66</b>
<b>Table 2-16: Reverse link: BC (band class) 6 .....</b>	<b>2-66</b>
<b>Table 2-17: Reverse link: BC (band class) 7 .....</b>	<b>2-67</b>
<b>Table 2-18: Forward and reverse link: BC (band class) 0, 1, 2, 3, 4, 5, 7, 8, and 9 .....</b>	<b>2-67</b>
<b>Table 2-19: Forward link: BC (band class) 6 .....</b>	<b>2-68</b>
<b>Table 2-20: Reverse link: BC (band class) 6 .....</b>	<b>2-68</b>
<b>Table 2-21: Reverse link: all band classes .....</b>	<b>2-69</b>
<b>Table 3-1: Measurement modes .....</b>	<b>3-1</b>
<b>Table 3-2: :CONFigure commands .....</b>	<b>3-2</b>
<b>Table 3-3: :DISPlay commands .....</b>	<b>3-2</b>
<b>Table 3-4: :FETCh commands .....</b>	<b>3-4</b>
<b>Table 3-5: :MMEMory commands .....</b>	<b>3-5</b>
<b>Table 3-6: :READ commands .....</b>	<b>3-5</b>
<b>Table 3-7: :SENSe commands .....</b>	<b>3-6</b>
<b>Table 3-8: :DISPlay command subgroups .....</b>	<b>3-17</b>
<b>Table 3-17: :SENSe command subgroups .....</b>	<b>3-75</b>

<b>Table A-1: cdma2000 forward link .....</b>	<b>A-1</b>
<b>Table A-2: cdma2000 reverse link .....</b>	<b>A-2</b>
<b>Table B-1: Factory default settings-:DISPlay commands .....</b>	<b>B-1</b>
<b>Table B-2: Factory default settings-:SENSe commands .....</b>	<b>B-2</b>
<b>Table C-1: Display format and scale .....</b>	<b>C-1</b>
<b>Table D-1: SCPI conformance information-:CONFigure commands ..</b>	<b>D-1</b>
<b>Table D-2: SCPI conformance information-:DISPlay commands .....</b>	<b>D-1</b>
<b>Table D-3: SCPI conformance information-:FETCH commands .....</b>	<b>D-3</b>
<b>Table D-4: SCPI conformance information-:MMEMory commands ..</b>	<b>D-3</b>
<b>Table D-5: SCPI conformance information-:READ commands .....</b>	<b>D-4</b>
<b>Table D-6: SCPI conformance information-:SENSe commands .....</b>	<b>D-4</b>

# Preface

This manual provides operating instructions for the WCA230A & WCA280A Portable Wireless Communication Analyzers Option 25 cdma2000 analysis software.

## About This Manual

This manual is composed of the following sections:

- *Getting Started* provides a product description.
- *Operating Basics* describes the measurement functions added by the option and explains how to set up the analyzer for each measurement mode.
- *Syntax and Commands* lists all command subsystems and describes all programming commands.
- *Appendices* provides additional information including specifications, factory default settings, and SCPI conformance information.

## Related Manuals

The following related documents are also available:

- The *WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual* (Tektronix part number 071-1253-xx) contains a tutorials that describes how to operate the analyzer. It also includes an in-depth discussion on how to more completely use the analyzer features.
- The *WCA230A & WCA280A Portable Wireless Communication Analyzers Programmer Manual* (Tektronix part number 071-1255-xx) contains an alphabetical listing of the programming commands and other information related to controlling the analyzer over the GPIB interface.

## Contacting Tektronix

<b>Phone</b>	1-800-833-9200*
<b>Address</b>	Tektronix, Inc. Department or name (if known) 14200 SW Karl Braun Drive P.O. Box 500 Beaverton, OR 97077 USA
<b>Web site</b>	<a href="http://www.tektronix.com">www.tektronix.com</a>
<b>Sales support</b>	1-800-833-9200, select option 1*
<b>Service support</b>	1-800-833-9200, select option 2*
<b>Technical support</b>	Email: <a href="mailto:techsupport@tektronix.com">techsupport@tektronix.com</a> 1-800-833-9200, select option 3* 6:00 a.m. - 5:00 p.m. Pacific time

- 
- \* This phone number is toll free in North America. After office hours, please leave a voice mail message.
  - Outside North America, contact a Tektronix sales office or distributor; see the Tektronix web site for a list of offices.



# Getting Started



# Getting Started

This section provides an overview of the product capabilities.

## Product Description

The WCA230A & WCA280A Wireless Communication Analyzers Option 25 is an analysis software option that adds transmitter measurements capability for cdma2000 forward link (3GPP2 C.S0010) and reverse link (3GPP2 C.S0011) to the analyzers.

You can perform the following cdma2000 measurements:

- Modulation accuracy
- Code domain power
- Channel power
- OBW (occupied bandwidth)
- ACPR (Adjacent channel power ratio)
- Spectrum emission mask
- Gated output power (reverse link only)
- Intermodulation
- CCDF
- Pilot to code channel

In addition, the option provides pre-defined measurement limits for the ACPR, spectrum emission mask, and gated output power measurements. Using these measurement limits, you can easily check that the input signal meets the specification.





# Operating Basics



# Functional Overview

This section provides an overview of the Option 25 measurement functions.

Figure 2-1 shows the measurement functions and how to access each measurement function from the front-panel menu key.




Figure 2-1: Menu diagram showing measurement functions available in Option 25

## Accessing a Measurement Function

All of the measurement functions available in Option 25 can be selected from the DEMOD (demodulation) mode.

Perform the following procedure to access any of the measurement functions:

1. Press the **DEMOD** menu key to open the DEMOD menu.
2. Press the **Standard...** side key to open the Standard menu.
3. Press the **cdma2000-Fwd** or **cdma2000-Rev** side key to open the MEASURE menu for the standard.
4. Press one of the side keys to select the measurement that you want to perform. If the desired measurement is not displayed on the current MEASURE menu, press the **Go to page 2 (of 2)** side key to open the next page.
5. If needed, set frequency, span, and amplitude of the input signal.

Refer to the *WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual* for information on how to set frequency, span, and amplitude.

# cdma2000 Forward Link Measurements

This section describes the functions and features of the cdma2000 forward link measurements. Each measurement description contains general information about the measurement, descriptions of the measurement displays and functions available through menu selections.

The information is divided into the following subsections:

- Modulation accuracy measurement
- Code domain power measurement
- Channel power measurement
- OBW measurement
- ACPR measurement
- Spectrum emission mask measurement
- Intermodulation measurement
- CCDF measurement
- Pilot to code channel measurement

---

**NOTE.** If you are not familiar with the operation of the WCA230A/WCA280A, refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual before reading this section.

---

## Modulation Accuracy Measurement

The modulation accuracy measurement measures Rho (ratio of the correlated power to the total power), EVM (Error Vector Magnitude), magnitude error, phase error, frequency error, and origin offset. Figure 2-2 shows an example of the modulation accuracy measurement.




Figure 2-2: Modulation accuracy measurement

### Display Elements

The following information is shown in the modulation accuracy measurement display:

- **Overview:** This view can contain power versus time or spectrogram.
- **Subview:** This view can contain spectrum, EVM, magnitude error, phase error, IQ power graph, and constellation.
- **Main view:** This view can contain modulation accuracy, EVM, magnitude error, phase error, and symbol table.

The display contents in each view can be changed using the VIEW DEFINE menu. Refer to *Changing the View Contents* on page 2-6 for more information about the VIEW DEFINE menu.

## Setting the Timing Parameters

You can set the following timing parameters using the TIMING menu. Press the **TIMING** key to open the TIMING menu.

- **Acquisition Length (chips):** Sets the acquisition length in chips. The range depends on the acquisition memory size and the span setting.
- **Acquisition Length (s):** Displays the acquisition length in seconds.
- **Acquisition History:** Specifies the number of the block to display and analyze. The latest block is number zero. Older blocks have larger negative numbers.
- **Analysis Interval:** Sets the analysis interval in chips. The range depends on the acquisition length setting.
- **Analysis Offset:** Sets the start point of the analysis with respect to the left end of the acquisition length in chips.
- **Spectrum Length:** Displays the time length for FFT processing of the spectrum displayed in the subview. This value is equivalent to one frame acquisition length.
- **Spectrum Offset:** Sets the beginning of Spectrum Length with respect to the left end of the acquisition length.

---

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for detailed information about the timing parameters.

---

## Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Analyze:** Performs analysis for the time slots in the analysis range.
- **Measurement Level:** Selects the measurement level for the measurement. You can select Chip (chip level) or Symbol (symbol level).
- **Radio Configuration...:** Selects the radio configuration for the measurement. You can select RC1/RC2 or RC3/RC4/RC5.
- **PN Offset:** Sets the PN offset in units of 64 chips. You can set the value from 0 to 511.
- **Select PCG:** Sets the PCG (power control group) for the measurement.
- **Select Code:** Sets the code in the PCG for the measurement. This setting is only available when Measurement Level is set to Symbol.
- **Limits...:** Sets the pass/fail limits for the modulation accuracy measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.
- **Active Channel Threshold:** Sets the active channel threshold level (in dB from the pilot) used for deciding whether a code channel is active or inactive. You can set the value from -50 dB to 50 dB.

- **IQ Swap:** Sets whether to swap the I and Q data streams before demodulation.
- **Measurement Filter...:** Selects the measurement filter to apply when calculating EVM and other modulation accuracy results. You can select None, cdma2000, or cdma2000+EQ (equalizer).
- **Walsh Code Length...:** Selects the Walsh code length. You can select Composite, 64, 32, 16, 8, 4, or 2. This setting is only available when Measurement Level is set to Symbol and Radio Configuration is set to RC3/RC4/RC5. When Radio Configuration is set to RC1/RC2, the Walsh code length is fixed at 64 and cannot be changed by the user.
- **QOF:** Sets the Walsh code quasi-orthogonal function. The choices are 0, 1, 2, or 3. This setting is only available when Measurement Level is set to Symbol and Radio Configuration is set to RC3/RC4/RC5.

## Changing the View Contents

You can change the view contents in the overview, subview, and main view using the **VIEW DEFINE** menu. Press the **DEFINE** key to display the **VIEW DEFINE** menu.

- **Show Views:** Selects the view style on the screen. You can select Single or Multi.
- **Overview Content...:** Selects a view to display in the overview. You can select Spectrogram or Waveform (power versus time).
- **Subview Content...:** Selects a view to display in the subview:
  - **Spectrum:** Displays spectrum of the measured signal.
  - **EVM:** Displays changes of EVM (Error Vector Magnitude) over time.
  - **MagErr:** Displays changes of magnitude error over time.
  - **PhaseErr:** Displays changes of phase error over time.
  - **IQ Power Graph:** Displays the code domain power for each symbol. Refer to *IQ Power Graph Display* on page 2-19.
  - **Constellation:** Displays the signal as an I-Q constellation.
- **Mainview Content...:** Selects a view to display in the main view. You can select Modulation Accuracy, EVM, MagErr, PhaseErr, or Symbol Table. Refer to *Scale and Format in the Main View* on page 2-7 for more information about the views.
- **Menu Off:** Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW:DEFINE** key.

## Scale and Format in the Main View

This subsection describes the scale settings and display format in the main view.

**Modulation Accuracy Display.** When you select Mainview Content from the VIEW DEFINE menu and then select Modulation Accuracy from the Mainview Content submenu, an IQ rectangular graph and the measured value for Rho, peak code domain error, rms and peak EVM, magnitude error, phase error, frequency error, IQ origin offset, and Tau are displayed (see Figure 2-3). The peak code domain error is displayed only when the Measurement Level menu item is set to Symbol, and Tau is displayed only when an external trigger signal is applied.




Figure 2-3: Modulation accuracy display

You can set the scale of the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Measurement Content...:** Selects vector or constellation display.

**Vector:** Selects vector display. A signal represented with phase and amplitude is displayed in rectangular (I and Q) coordinates. The red point indicates the symbol position on the measured signal and the yellow trace indicates the locus of the signal between symbols.

**Constellation:** Selects constellation display. It is the same as the vector display, except that only symbols of the measured signal are indicated in red, and the locus between symbols is not shown. The cross marks indicate symbol positions of an ideal signal.

---

**NOTE.** *I and Q signals are normalized to prevent the scale from changing when signal attenuation changes.*

---

**EVM Display.** When you select Mainview Content from the VIEW DEFINE menu and then select EVM from the Mainview Content submenu, changes of EVM (Error Vector Magnitude) over time are displayed for each chip or symbol (see Figure 2-4).




Figure 2-4: EVM display

You can set the scale of the display using the VIEW SCALE menu. Press the SCALE key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis (number of chips or symbols).
- **Horizontal Start:** Sets the chip number or symbol number of the first (left) value of the horizontal axis.
- **Vertical Scale:** Sets the scale of the vertical axis.
- **Vertical Start:** Sets the minimum (bottom) value of the vertical axis.
- **Full Scale:** Sets the scale of vertical axis to the default full-scale value.
- **Measurement Content...:** Selects the display content in the main view. You can select EVM, MagErr, or PhaseErr. This selection can also be made from Mainview Content in the VIEW DEFINE menu.

**MagErr Display.** When you select Mainview Content from the VIEW DEFINE menu and then select MagErr from the Mainview Content submenu, changes of magnitude error over time are displayed for each chip or symbol (see Figure 2-5).




Figure 2-5: MagErr display

You can set the scale of the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis automatically to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis (number of chips or symbols).
- **Horizontal Start:** Sets the chip number or symbol number of the first (left) value of the horizontal axis.
- **Vertical Scale:** Sets the scale of the vertical axis.
- **Vertical Offset:** Sets the offset value of the vertical axis. You can set the value from -200% to 200%.
- **Full Scale:** Sets the scale of vertical axis to the default full-scale value.
- **Measurement Content...:** Selects the display content in the main view. You can select EVM, MagErr, or PhaseErr. This selection can also be made from Mainview Content in the VIEW DEFINE menu.

**PhaseErr Display.** When you select Mainview Content from the VIEW DEFINE menu and then select PhaseErr from the Mainview Content submenu, changes of phase error over time are displayed for each chip or symbol (see Figure 2-6).




Figure 2-6: PhaseErr display

You can set the scale of the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis automatically to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis (number of chips or symbols).
- **Horizontal Start:** Sets the chip number or symbol number of the first (left) value of the horizontal axis.
- **Vertical Scale:** Sets the scale of the vertical axis.
- **Vertical Offset:** Sets the offset value of the vertical axis. You can set the value from -450 to 450 degrees.
- **Full Scale:** Sets the scale of vertical axis to the default full-scale value.
- **Measurement Content...:** Selects the display content in the main view. You can select EVM, MagErr, or PhaseErr. This selection can also be made from Mainview Content in the VIEW DEFINE menu.

**Symbol Table Display.** When you select Mainview Content from the VIEW DEFINE menu and then select Symbol Table from the Mainview Content submenu, the symbol table is displayed (see Figure 2-7). This display is only available when the Measurement Level menu item is set to Symbol.




Figure 2-7: Symbol table display

You can set the radix for the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Radix...:** Sets the radix for displaying the table. You can select Hex (hexadecimal), Oct (octal), or Bin (binary).

## Code Domain Power Measurement

The code domain power measurement measures the distribution of signal power across the set of code channels, normalized to the total signal power. This measurement allows you to verify that each code channel is operating at its proper level. Figure 2-8 shows an example of the code domain power measurement.




Figure 2-8: Code domain power measurement

### Display Elements

The following information is shown in the code domain power measurement display:

- **Overview:** This view can contain power versus time or spectrogram.
- **Subview:** This view can contain spectrum, EVM, magnitude error, phase error, IQ power graph, and constellation.
- **Main view:** This view can contain code domain power, power codogram, and IQ power graph. The view also lists the following measurement results:
  - Total power
  - Pilot power
  - Active code power versus pilot
  - Active/inactive code power

The display contents in each view can be changed using the VIEW DEFINE menu. Refer to *Changing the View Contents* on page 2-14 for more information about the VIEW DEFINE menu.

## Setting the Timing Parameters

You can set the following timing parameters using the TIMING menu. Press the **TIMING** key to open the TIMING menu.

- **Acquisition Length (chips):** Sets the acquisition length in chips. The range depends on the acquisition memory size and the span setting.
- **Acquisition Length (s):** Displays the acquisition length in seconds.
- **Acquisition History:** Specifies the number of the block to display and analyze. The latest block is number zero. Older blocks have larger negative numbers.
- **Analysis Interval:** Sets the analysis interval in chips. The range depends on the acquisition length setting.
- **Analysis Offset:** Sets the start point of the analysis with respect to the left end of the acquisition length in chips.
- **Spectrum Length:** Displays the time length for FFT processing of the spectrum displayed in the subview. This value is equivalent to one frame acquisition length.
- **Spectrum Offset:** Sets the beginning of Spectrum Length with respect to the left end of the acquisition length.

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for detailed information about the timing parameters.

## Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Analyze:** Performs analysis for the time slots in the analysis range.
- **Measurement Level:** Selects the measurement level for the measurement. You can select Chip (chip level) or Symbol (symbol level). This setting is only available when Mainview Content in the VIEW DEFINE menu is set to IQ Power Graph.
- **Radio Configuration....:** Selects the radio configuration for the measurement. You can select RC1/RC2 or RC3/RC4/RC5.
- **PN Offset:** Sets the PN offset in units of 64 chips. You can set the value from 0 to 511.
- **Select PCG:** Sets the PCG (power control groups) for the measurement.
- **Select Code:** Sets the code in the PCG for the measurement.

- **Limits....**: Sets the pass/fail limits for the code domain power measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.
- **Active Channel Threshold**: Sets the active channel threshold level (in dB from the pilot) used for deciding whether a code channel is active or inactive. You can set the value from -50 dB to 50 dB.
- **IQ Swap**: Sets whether to swap the I and Q data streams before demodulation.
- **Measurement Filter....**: Selects the measurement filter to apply when calculating code domain power results. You can select None, cdma2000, or cdma2000+EQ (equalizer).
- **Walsh Code Length....**: Selects the Walsh code length. You can select Composite, 64, 32, 16, 8, 4, or 2. This setting is only available when Radio Configuration is set to RC3/RC4/RC5. When Radio Configuration is set to RC1/RC2, the Walsh code length is fixed at 64 and cannot be changed by the user.
- **QOF**: Sets the Walsh code quasi-orthogonal function. The choices are 0, 1, 2, or 3. This setting is only available when Radio Configuration is set to RC3/RC4/RC5.

## Changing the View Contents

You can change the contents in the overview, subview, and main view using the VIEW DEFINE menu. Press the **DEFINE** key to display the VIEW DEFINE menu.

- **Show Views**: Selects the view style on the screen. You can select Single or Multi.
- **Overview Content....**: Selects a view to display in the overview. You can select Spectrogram or Waveform (power versus time).
- **Subview Content....**: Selects a view to display in the subview:
  - **Spectrum**: Displays spectrum of the input signal.
  - **EVM**: Displays changes of EVM (Error Vector Magnitude) over time.
  - **MagErr**: Displays changes of magnitude error over time.
  - **PhaseErr**: Displays changes of phase error over time.
  - **IQ Power Graph**: Displays the code domain power for each symbol. Refer to *IQ Power Graph Display* on page 2-19.
  - **Constellation**: Displays the signal as an I-Q constellation.
- **Mainview Content....**: Selects a view to display in the main view. You can select Code Domain Power, Power Codogram, or IQ Power Graph. Refer to *Scale and Format in the Main View* on page 2-15 for more information about the views.

- **Code Order...**: Sets the way that code channels are arranged on the display. You can select Hadamard or BitReverse.
- **Menu Off**: Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW:DEFINE** key.

## Scale and Format in the Main View

This subsection describes the scale settings and display format in the main view.

**Code Domain Power Display.** When you select Mainview Content from the VIEW DEFINE menu and then select Code Domain Power from the Mainview Content submenu, the code domain power for code channels is displayed (see Figure 2-9).




Figure 2-9: Code domain power display

In the code domain power display, the I and Q power bars are distinguished by using different colors as follows:

- Blue: pilot channel
- Red: active channel
- Yellow: inactive channel

You can set the scale of the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis automatically to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis. The range is dependent on the Radio Configuration setting.
- **Horizontal Start:** Sets the channel number of the first (left) value of the horizontal axis.
- **Vertical Scale:** Sets the scale of the vertical axis. You can set the value from 100  $\mu$ dB to 100 dB.
- **Vertical Stop:** Sets the maximum (top) value of the vertical axis. You can set the value from -100 dB to 100 dB.
- **Full Scale:** Sets the scale of the vertical axis to the default full-scale value.
- **Y Axis...:** Selects whether to represent the vertical (amplitude) axis with relative values or absolute values. When you select Relative, the vertical axis represents the power relative to the total power of all channels. When you select Absolute, the vertical axis represents the absolute power of each channel.
- **Graph Number:** Selects the number of graphs to be displayed in the screen. You can select 1 or 2.
- **View Data....:** Sets which channels to display when 1 is selected in the Graph Number menu item. You can select I, Q, or IandQ.

**Power Codogram Display.** When you select Mainview Content from the VIEW DEFINE menu and then select Power Codogram from the Mainview Content submenu, the code domain power is displayed in spectrogram (see Figure 2-10).




Figure 2-10: Power codogram display

You can set the scale of the display using the VIEW SCALE menu. Press the SCALE key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis. The range is dependent on the Radio Configuration setting.
- **Horizontal Start:** Sets the channel number of the first (left) value of the horizontal axis.
- **Vertical Size:** Sets the scale of the vertical axis.

- **Vertical Start:** Sets the frame value at the bottom of the vertical axis.
- **Color Scale:** Sets the scale (the value separating the minimum power value from the maximum power value) of the color axis. The choices are 5, 10, 20, and 50 dB.
- **Color Stop:** Sets the stop value of the color axis.
- **Full Scale:** Sets the maximum value of the color axis to the reference level.
- **Y Axis...:** Selects whether to represent the Y (color) axis with relative values or absolute values. When you select Relative, the Y axis represents the power relative to the total power of all channels. When you select Absolute, the Y axis represents the absolute power of each channel.
- **Graph Number:** Selects the number of graphs to be displayed in the screen. You can select 1 or 2.
- **View Data...:** Sets which channels to display when 1 is selected in the Graph Number menu item. You can select I, Q, or IandQ.

**IQ Power Graph Display.** When you select Mainview Content from the VIEW DEFINE menu and then select IQ Power Graph from the Mainview Content submenu, I and Q powers over time is displayed for each chip or symbol (see Figure 2-11).




Figure 2-11: IQ power graph display

You can set the scale of the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis automatically to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis (number of chips or symbols).
- **Horizontal Start:** Sets the chip or symbol number of the first (left) value of the horizontal axis.

- **Vertical Scale:** Sets the scale of the vertical axis. You can set the value from 100 µdB to 100 dB.
- **Vertical Stop:** Sets the maximum (top) value of the vertical axis. You can set the value from -100 dB to 100 dB.
- **Full Scale:** Sets the scale of the vertical axis to the default full scale value.
- **Y Axis...:** Selects whether to represent the vertical (amplitude) axis with relative values or absolute values. When you select Relative, the vertical axis represents the power relative to the total power of all channels. When you select Absolute, the vertical axis represents the absolute power of each channel.
- **Graph Number:** Selects the number of graphs to be displayed in the screen. You can select 1 or 2.
- **View Data...:** Sets which channels to display when 1 is selected in the Graph Number menu item. You can select I, Q, or IandQ.

## Channel Power Measurement

The channel power measurement measures the channel power within a specified bandwidth and the power spectral density in dBm/Hz. Figure 2-12 shows an example of the channel power measurement.




Figure 2-12: Channel power measurement

### Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Channel Bandwidth:** Sets the frequency range for the measurement.
- **Measurement Filter Shape:** Sets the filter to be used for the measurement. You can select Rect (Rectangular), Gaussian, Nyquist, or Root Nyquist.
- **Rolloff Ratio:** Enters the rolloff ratio when the Nyquist or Root Nyquist filter is selected. You can set the value from 0.0001 to 1. The default value is 0.5.
- **Limits...:** Sets the pass/fail limit for the channel power measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for information about the scale settings for the display.

## OBW Measurement

The OBW (Occupied Bandwidth) measurement measures the frequency bandwidth, using the ratio you specify for carrier signal power/power within the span setting. Figure 2-13 shows an example of the OBW measurement.




Figure 2-13: OBW measurement

### Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Power Ratio:** Specifies the power ratio of the carrier and span regions for calculating OBW. You can set the value from 80 to 99.99%. The default value is 99%.
- **Limits...:** Sets the pass/fail limits for the OBW measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for information about the scale settings for the display.

## ACPR Measurement

The ACPR (Adjacent Channel Power Ratio) measurement measures the ratio of carrier signal power to the signal power in an adjacent channel (leakage signal). Figure 2-14 shows an example of the ACPR measurement.




Figure 2-14: ACPR measurement

### Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Main Channel Bandwidth:** Sets the bandwidth of the main channel.
- **Measurement Filter Shape...:** Sets the filter to be used for the measurement. You can select Rect (Rectangular), Gaussian, Nyquist, or Root Nyquist.
- **Rolloff Ratio:** Enters the rolloff ratio when the Nyquist or Root Nyquist filter is selected. You can set the value from 0.0001 to 1. The default value is 0.5.
- **Scroll Table:** Scrolls the table displayed in the view.
- **Limits:** Sets the pass/fail limit for the ACPR measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for information about the scale settings for the display.

## Spectrum Emission Mask Measurement

The spectrum emission mask measurement verifies that the base station is not transmitting excessive power outside of its designated channel. Figure 2-15 shows an example of the spectrum emission mask measurement.




Figure 2-15: Spectrum emission mask measurement

### Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Measurement...:** Sets the limit table used for limit testing. You can select Offset From Channel or Inband Spurious. For Offset From Channel, frequency zones are specified by the difference from the center frequency. For Inband Spurious, frequency zones are specified by the absolute frequency values.
- **Ref. Channel Select:** Selects the reference mode used to measure the spectrum emission level. You can select Auto or Man (manual). For Auto, the reference level is measured from the input signal for the specified channel bandwidth. For Man, you can set the reference level in the Ref. Channel Level menu item.
- **Ref. Channel Level:** Sets the reference level used to measure the spectrum emission level. You can set the value from -150 dBm to 30 dBm. This setting is only available when Ref. Channel Select is set to Man (manual).
- **Channel Bandwidth:** Sets the channel bandwidth for the measurement.

- **Measurement Filter Shape...:** Sets the filter to be used for the measurement. You can select Rect (Rectangular), Gaussian, Nyquist, or Root Nyquist. This setting is only available when Ref. Channel Select is set to Auto.
- **Rolloff Ratio:** Enters the rolloff ratio when the Nyquist or Root Nyquist filter is selected. You can set the value from 0.0001 to 1. The default value is 0.5. This setting is only available when Ref. Channel Select is set to Auto.
- **Limits...:** Sets the pass/fail limits for the intermodulation measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.
- **Scroll Table:** Scrolls the table displayed in the view.

---

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for information about the scale settings for the display.

---

## Changing the View Contents

You can change the contents in the view using the VIEW DEFINE menu. Press the **DEFINE** key to display the VIEW DEFINE menu.

- **Grid Style:** Sets the grid style in the view. You can select Off, Fix, or Flex. For Flex, the grid is changed depending on frequency or span setting.
- **Menu Off:** Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW: DEFINE** key.

## Intermodulation Measurement

The intermodulation measurement measures the third-order and fifth-order harmonic distortion components of a modulated signal. Figure 2-16 shows an example of the intermodulation measurement.




Figure 2-16: Intermodulation measurement

### Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **2nd Channel Offset:** Sets the center frequency of the second channel. Use this menu item when the interfering carrier may be outside of the analysis span.
- **Main Channel Integration BW:** Sets the integration bandwidth. You can set the value from 500 kHz to 5 MHz.
- **Measurement Filter Shape...:** Sets the filter to be used for the measurement. You can select Rect (Rectangular), Gaussian, Nyquist, or Root Nyquist.
- **Rolloff Ratio:** Enters the rolloff ratio when the Nyquist or Root Nyquist filter is selected. You can set the value from 0.0001 to 1. The default value is 0.5.

- **Limits:** Sets the pass/fail limits for the intermodulation measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for information about the scale settings for the display.

## CCDF Measurement

The CCDF (Complementary Cumulative Distribution Function) measurement displays the peak-to-average power ratio along the horizontal axis, and the probability that the ratio is exceeded along the vertical axis. This display is useful in designing digital communications systems. Figure 2-17 shows an example of the CCDF measurement.




Figure 2-17: CCDF measurement (single view)

## Setting the Timing Parameters

You can set the following timing parameters using the TIMING menu. Press the **TIMING** key to open the TIMING menu.

- **Acquisition Length (s):** Sets the acquisition length in seconds.
- **Acquisition History:** Specifies the number of the block to display and analyze. The latest block is number zero. Older blocks have larger negative numbers.
- **Spectrum Length:** Display the time length for FFT processing of the spectrum displayed in the subview. This value is equivalent to one frame acquisition length.
- **Spectrum Offset:** Sets the beginning of Spectrum Length with respect to the left end of the acquisition length.
- **Output Trigger Indicator:** Selects whether to enable the output trigger indicator.

---

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for detailed information about the time parameters.

---

## Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Display Gaussian Line:** Selects whether to display the Gaussian line on the graticule.
- **Display Reference Line:** Selects whether to display the most recently stored reference line on the graticule.
- **Store Reference Line:** Stores a new reference line.
- **Reset Measurement:** Restart the CCDF measurement. When you press this key, the CCDF accumulation counter on the upper right side of the display is reset to 0.
- **CCDF Auto-Scaling:** Selects whether to automatically set the scaling of the horizontal axis. When you set it to On, the signal peak value is displayed as the maximum value on the right edge of the graticule. When you set it to Off, the scaling of the horizontal axis can be set manually with CCDF Scale. The default value is Off.
- **CCDF Scale:** Sets the full-scale value of the horizontal axis of the CCDF display when CCDF Auto-Scaling is set to Off. You can set the value from 1dB to 100 dB.
- **Threshold:** Sets the threshold for the measurement. You can set the value from -250 dBm to 130 dBm.
- **Limits...:** When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.

## Changing the View Contents

You can change the contents in the overview using the VIEW DEFINE menu. Press the **DEFINE** key to display the VIEW DEFINE menu.

- **Show Views:** Sets the view style on the screen. You can select Single or Multi. When you set it to Multi, the CCDF, spectrum, and power versus time of the measured signal are displayed simultaneously.
- **Overview Content...:** Selects a view to display in the overview. You can select Spectrogram or Waveform (power versus time).
- **Menu Off:** Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW:DEFINE** key.

## Scale in the Main View

You can set the scale in the main view using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis automatically to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis.
- **Horizontal Start:** Sets the minimum (left) value of the horizontal axis.
- **Vertical Stop:** Sets the maximum (top) value of the vertical axis. The setting ranges are twice the Vertical Start value to 100% in a 1-2-5 sequence.
- **Vertical Start:** Sets the minimum (bottom) value of the vertical axis. The setting ranges are  $10^{-6}$  to half the Vertical Stop value in a 1-2-5 sequence.
- **Full Scale:** Sets the scale of the vertical axis to the default full scale value.
- **Sub Grid:** Selects whether to display the sub-grid on the graticule.




Figure 2-18: Scale settings in the CCDF display

## Pilot to Code Channel Measurement

The pilot to code channel measurement measures the time difference between the pilot channel and other code channels detected in the received signal. Figure 2-19 shows an example of the pilot to code channel measurement.




Figure 2-19: Pilot to code channel measurement

### Display Elements

The following information is shown in the pilot to code channel measurement display:

- **Overview:** This view can contain power versus time or spectrogram.
- **Subview:** This view can contain spectrum, EVM, magnitude error, phase error, and constellation.
- **Main view:** This view lists the following measurement results:
  - Power level
  - Timing referred to the pilot channel
  - Phase referred to the pilot channel
  - Code domain error

The display content in the subview can be changed using the VIEW DEFINE menu. Refer to *Changing the View Contents* on page 2-32 for more information about the VIEW DEFINE menu.

## Setting the Timing Parameters

You can set the following timing parameters using the TIMING menu. Press the **TIMING** key to open the TIMING menu.

- **Acquisition Length (chips):** Sets the acquisition length in chips. The range depends on the acquisition memory size and the span setting.
- **Acquisition Length (s):** Displays the acquisition length in seconds.
- **Acquisition History:** Specifies the number of the block to display and analyze. The latest block is number zero. Older blocks have larger negative numbers.
- **Analysis Interval:** Sets the analysis interval in chips. The range depends on the acquisition length setting.
- **Analysis Offset:** Sets the start point of the analysis with respect to the left end of the acquisition length in chips.
- **Spectrum Length:** Displays the time length for FFT processing of the spectrum displayed in the subview. This value is equivalent to one frame acquisition length.
- **Spectrum Offset:** Sets the beginning of Spectrum Length with respect to the left end of the acquisition length.

---

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for detailed information about the timing parameters.

---

## Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Analyze:** Performs analysis for the time slots in the analysis range.
- **Radio Configuration....:** Selects the radio configuration for the measurement. You can select RC1/RC2 or RC3/RC4/RC5.
- **PN Offset:** Sets the PN offset in units of 64 chips. You can set the value from 0 to 511.
- **Select PCG:** Sets the PCG (power control groups) for the measurement.
- **Limits....:** Sets the pass/fail limits for the pilot to code channel measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.
- **Scroll Table:** Scrolls the table displayed in the view.
- **Active Channel Threshold:** Sets the active channel threshold level (in dB from the pilot) used for deciding whether a code channel is active or inactive. You can set the value from -50 dB to 50 dB.
- **IQ Swap:** Sets whether to swap the I and Q data streams before demodulation.

- **Measurement Filter...:** Selects the measurement filter to apply when calculating pilot to code channel results. You can select None, cdma2000, or cdma2000+EQ (equalizer).
- **Walsh Code Length...:** Selects the Walsh code length. You can select Composite, 64, 32, 16, 8, 4, or 2. This setting is only available when Radio Configuration is set to RC3/RC4/RC5.
- **QOF:** Sets the Walsh code quasi-orthogonal function. The choices are 0, 1, 2, or 3. This setting is only available when Radio Configuration is set to RC3/RC4/RC5. When Radio Configuration is set to RC1/RC2, the Walsh code length is fixed at 64 and cannot be changed by the user.

### Changing the View Contents

You can change the contents in the overview and subview using the VIEW DEFINE menu. Press the **DEFINE** key to display the VIEW DEFINE menu.

- **Show Views:** Sets the view style on the screen. You can select Single or Multi.
- **Overview Content...:** Selects a view to display in the overview. You can select Spectrogram or Waveform (spectrum).
- **Subview Content...:** Selects a view to display in the subview:
  - **Spectrum:** Displays spectrum of the input signal.
  - **EVM:** Displays changes of EVM (Error Vector Magnitude) over time.
  - **MagErr:** Displays changes of magnitude error over time.
  - **PhaseErr:** Displays changes of phase error over time.
  - **Constellation:** Displays the signal as an I-Q constellation.
- **Menu Off:** Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW: DEFINE** key.

# cdma2000 Reverse Link Measurements

This section describes the functions and features of the cdma2000 reverse link measurements. Each measurement description contains general information about the measurement, descriptions of the measurement displays and functions available through menu selections.

The information is divided into the following subsections:

- Modulation accuracy measurement
- Code domain power measurement
- Pilot to code channel measurement
- Gated output power measurement

The following measurement items available in the cdma2000 reverse link measurements are the same as those in the cdma2000 forward link measurements. Refer to *cdma2000 Forward Link Measurements* beginning on page 2-3.

- Channel power measurement
- OBW measurement
- ACPR measurement
- Spectrum emission mask measurement
- Intermodulation measurement
- CCDF measurement

---

**NOTE.** If you are not familiar with the operation of the WCA230A/WCA280A, refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual before reading this section.

---

## Modulation Accuracy Measurement

The modulation accuracy measurement measures Rho (ratio of the correlated power to the total power), EVM (Error Vector Magnitude), magnitude error, phase error, frequency error, and origin offset. Figure 2-20 shows an example of the modulation accuracy measurement.




Figure 2-20: Modulation accuracy measurement-reverse link

### Display Elements

The following information is shown in the modulation accuracy measurement display:

- **Overview:** This view can contain power versus time or spectrogram.
- **Subview:** This view can contain spectrum, EVM, magnitude error, phase error, IQ power graph, and constellation.
- **Main view:** This view can contain modulation accuracy, EVM, magnitude error, phase error, and symbol table.

The display contents in each view can be changed using the VIEW DEFINE menu. Refer to *Changing the View Contents* on page 2-36 for more information about the VIEW DEFINE menu.

## Setting Timing Parameters

You can set the following timing parameters using the TIMING menu. Press the **TIMING** key to open the TIMING menu.

- **Acquisition Length (chips):** Sets the acquisition length in chips. The range depends on the acquisition memory size and the span setting.
- **Acquisition Length (s):** Displays the acquisition length in seconds.
- **Acquisition History:** Specifies the number of the block to display and analyze. The latest block is number zero. Older blocks have larger negative numbers.
- **Analysis Interval:** Sets the analysis interval in chips. The range depends on the acquisition length setting.
- **Analysis Offset:** Sets the start point of the analysis with respect to the left end of the acquisition length in chips.
- **Spectrum Length:** Displays the time length for FFT processing of the spectrum displayed in the subview. This value is equivalent to one frame acquisition length.
- **Spectrum Offset:** Sets the beginning of Spectrum Length with respect to the left end of the acquisition length.

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for detailed information about the timing parameters.

## Setting Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Analyze:** Performs analysis for the time slots in the analysis range.
- **Measurement Level:** Selects the measurement level for the measurement. You can select Chip (chip level) or Symbol (symbol level). This setting is only available when Radio Configuration is set to RC3/RC4.
- **Radio Configuration....:** Selects the radio configuration for the measurement. You can select RC1/RC2 or RC3/RC4.

**NOTE.** When you select RC1/RC2 in this measurement, you cannot access the code domain power measurement or pilot to code channel measurement.

- **Select PCG:** Sets the PCG (power control group) for the measurement.
- **Select Code:** Sets the code in the PCG for the measurement. This setting is only available when Radio Configuration is set to RC3/RC4 and Measurement Level is set to Symbol.
- **Limits....:** Sets the pass/fail limits for the modulation accuracy measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.

- **Active Channel Threshold:** Sets the active channel threshold level (in dB from the pilot) used for deciding whether a code channel is active or inactive. You can set the value from -100 dB to 0 dB. This setting is only available when Radio Configuration is set to RC3/RC4.
- **IQ Swap:** Sets whether to swap the I and Q data streams before demodulation.
- **Measurement Filter...:** Selects the measurement filter to apply when calculating EVM and other modulation accuracy results. You can select None, cdma2000, or cdma2000+EQ (equalizer).
- **Walsh Code Length...:** Selects the Walsh code length. You can select Composite, 64, 32, 16, 8, 4, or 2. This setting is only available when Measurement Level is set to Symbol and Radio Configuration is set to RC3/RC4. When Radio Configuration is set to RC1/RC2, the Walsh code length is fixed at 64 and cannot be changed by the user.

#### Changing the View Contents

You can change the view contents in the overview, subview, and main view using the **VIEW DEFINE** menu. Press the **DEFINE** key to display the **VIEW DEFINE** menu.

- **Show Views:** Selects the view style on the screen. You can select Single or Multi.
- **Overview Content...:** Selects a view to display in the overview. You can select Spectrogram or Waveform (power versus time).
- **Subview Content...:** Selects a view to display in the subview:
  - **Spectrum:** Displays spectrum of the measured signal.
  - **EVM:** Displays changes of EVM (Error Vector Magnitude) over time.
  - **MagErr:** Displays changes of magnitude error over time.
  - **PhaseErr:** Displays changes of phase error over time.
  - **IQ Power Graph:** Displays the code domain power for each symbol. Refer to *IQ Power Graph Display* on page 2-19.
  - **Constellation:** Displays the signal as an I-Q constellation.
- **Mainview Content...:** Selects a view to display in the main view. You can select Modulation Accuracy, EVM, MagErr, PhaseErr, or Symbol Table. Refer to *Scale and Format in the Main View* on page 2-36 for more information about the views.
- **Menu Off:** Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW:DEFINE** key.

#### Scale and Format in the Main View

This subsection describes the scale settings and display format in the main view.

**Modulation Accuracy Display.** When you select Mainview Content from the VIEW DEFINE menu and then select Modulation Accuracy from the Mainview Content submenu, an IQ rectangular graph and the measured value for Rho, peak code domain error, rms and peak EVM, magnitude error, phase error, frequency error, and IQ origin offset are displayed (see Figure 2-21). The peak code domain error is displayed only when the Measurement Level menu item is set to Symbol.




Figure 2-21: Modulation accuracy display-reverse link

You can set the scale of the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Measurement Content...:** Selects vector or constellation display.

**Vector:** Selects vector display. A signal represented with phase and amplitude is displayed in rectangular (I and Q) coordinates. The red point indicates the symbol position on the measured signal, and the yellow trace indicates the locus of signal between symbols.

**Constellation:** Selects constellation display. It is the same as the vector display, except that only symbols of the measured signal are indicated in red, and the locus between symbols is not shown. The cross marks indicate symbol positions of an ideal signal.

---

**NOTE.** *I and Q signals are normalized to prevent the scale from changing when signal attenuation changes.*

---

**EVM Display.** When you select Mainview Content from the VIEW DEFINE menu and then select EVM from the Mainview Content submenu, changes of EVM (Error Vector Magnitude) over time are displayed for each chip or symbol (see Figure 2-22).




Figure 2-22: EVM display-reverse link

You can set the scale of the display using the VIEW SCALE menu. Press the SCALE key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis (number of chips or symbols).
- **Horizontal Start:** Sets the chip number or symbol number of the first (left) value of the horizontal axis.
- **Vertical Scale:** Sets the scale of the vertical axis.
- **Vertical Start:** Sets the minimum (bottom) value of the vertical axis.
- **Full Scale:** Sets the scale of vertical axis to the default full-scale value.
- **Measurement Content...:** Selects the display content in the main view. You can select EVM, MagErr, or PhaseErr. This selection can also be made from Mainview Content in the VIEW DEFINE menu.

**MagErr Display.** When you select Mainview Content from the VIEW DEFINE menu and then select MagErr from the Mainview Content submenu, changes of magnitude error over time are displayed for each chip or symbol (see Figure 2-23).




Figure 2-23: MagErr display-reverse link

You can set the scale of the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis automatically to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis (number of chips or symbols).
- **Horizontal Start:** Sets the chip number or symbol number of the first (left) value of the horizontal axis.
- **Vertical Scale:** Sets the scale of the vertical axis.
- **Vertical Offset:** Sets the offset value of the vertical axis. You can set the value from -200% to 200%.
- **Full Scale:** Sets the scale of vertical axis to the default full-scale value.
- **Measurement Content...:** Selects the display content in the main view. You can select EVM, MagErr, or PhaseErr. This selection can also be made from Mainview Content in the VIEW DEFINE menu.

**PhaseErr Display.** When you select Mainview Content from the VIEW DEFINE menu and then select PhaseErr from the Mainview Content submenu, changes of phase error over time are displayed for each chip or symbol (see Figure 2-24).




Figure 2-24: PhaseErr display-reverse link

You can set the scale of the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis automatically to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis (number of chips or symbols).
- **Horizontal Start:** Sets the chip number or symbol number of the first (left) value of the horizontal axis.
- **Vertical Scale:** Sets the scale of the vertical axis.
- **Vertical Offset:** Sets the offset value of the vertical axis. You can set the value from -450 to 450 degrees.
- **Full Scale:** Sets the scale of vertical axis to the default full-scale value.
- **Measurement Content...:** Selects the display content in the main view. You can select EVM, MagErr, or PhaseErr. This selection can also be made from Mainview Content in the VIEW DEFINE menu.

**Symbol Table Display.** When you select Mainview Content from the VIEW DEFINE menu and then select Symbol Table from the Mainview Content submenu, the symbol table is displayed (see Figure 2-25). This display is only available when the Measurement Level menu item is set to Symbol.




Figure 2-25: Symbol table display-reverse link

You can set the radix for the display using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Radix...:** Sets the radix for displaying the table. You can select Hex (hexadecimal), Oct (octal), or Bin (binary).

## Code Domain Power Measurement

**NOTE.** To access the code domain power measurement, you need to set the radio configuration setting to RC3/RC4 in the modulation accuracy measurement.

The code domain power measurement measures the distribution of signal power across the set of code channels, normalized to the total signal power. This measurement allows you to verify that each code channel is operating at its proper level. Figure 2-26 shows an example of the code domain power measurement.




Figure 2-26: Code domain power measurement-reverse link

<b>Display Elements</b>	<p>The following information is shown in the code domain power measurement display:</p> <ul style="list-style-type: none"> <li>■ <b>Overview:</b> This view can contain power versus time or spectrogram.</li> <li>■ <b>Subview:</b> This view can contain spectrum, EVM, magnitude error, phase error, IQ power graph, and constellation.</li> <li>■ <b>Main view:</b> This view can contain code domain power, power codogram, and IQ power graph. This view also lists the following measurement results:</li> </ul>
	<p>Total power  Active code power versus total power  Active/inactive code power</p> <p>The display contents in each view can be changed using the VIEW DEFINE menu. Refer to <i>Changing the View Contents</i> on page 2-44 for more information about the VIEW DEFINE menu.</p>

---

<b>Setting the Timing Parameters</b>	<p>You can set the following timing parameters using the TIMING menu. Press the <b>TIMING</b> key to open the TIMING menu.</p>
	<ul style="list-style-type: none"> <li>■ <b>Acquisition Length (chips):</b> Sets the acquisition length in chips. The range depends on the acquisition memory size and the span setting.</li> <li>■ <b>Acquisition Length (s):</b> Displays the acquisition length in seconds.</li> <li>■ <b>Acquisition History:</b> Specifies the number of the block to display and analyze. The latest block is number zero. Older blocks have larger negative numbers.</li> <li>■ <b>Analysis Interval:</b> Sets the analysis interval in chips. The range depends on the acquisition length setting.</li> <li>■ <b>Analysis Offset:</b> Sets the start point of the analysis with respect to the left end of the acquisition length in chips.</li> <li>■ <b>Spectrum Length:</b> Displays the time length for FFT processing of the spectrum displayed in the subview. This value is equivalent to one frame acquisition length.</li> <li>■ <b>Spectrum Offset:</b> Sets the beginning of Spectrum Length with respect to the left end of the acquisition length.</li> </ul>

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for detailed information about the timing parameters.

## Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Analyze:** Performs analysis for the time slots in the analysis range.
- **Radio Configuration...:** Select the radio configuration for the measurement. You can select only RC3/RC4.
- **Select PCG:** Sets the PCG (power control group) for the measurement.
- **Select Code:** Sets the code in the PCG for the measurement.
- **Limits...:** Sets the pass/fail limits for the code domain power measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.
- **Active Channel Threshold:** Sets the active channel threshold level (in dB from the pilot) used for deciding whether a code channel is active or inactive. You can set the value from -50 dB to 50 dB.
- **IQ Swap:** Sets whether to swap the I and Q data streams before demodulation.
- **Measurement Filter...:** Selects the measurement filter to apply when calculating code domain power results. You can select None, cdma2000, or cdma2000+EQ (equalizer).
- **Walsh Code Length...:** Selects the Walsh code length. You can select Composite, 64, 32, 16, 8, 4, or 2. This setting is only available when Measurement Level is set to Symbol and Radio Configuration is set to RC3/RC4. When Radio Configuration is set to RC1/RC2, the Walsh code length is fixed at 64 and cannot be changed by the user.

## Changing the View Contents

You can change the contents in the overview, subview, and main view using the VIEW DEFINE menu. Press the **DEFINE** key to display the VIEW DEFINE menu.

- **Show Views:** Selects the view style on the screen. You can select Single or Multi.
- **Overview Content...:** Selects a view to display in the overview. You can select Spectrogram or Waveform (power versus time).
- **Subview Content...:** Selects a view to display in the subview:
  - **Spectrum:** Displays spectrum of the input signal.
  - **EVM:** Displays changes of EVM (Error Vector Magnitude) over time.
  - **MagErr:** Displays changes of magnitude error over time.
  - **PhaseErr:** Displays changes of phase error over time.
  - **IQ Power Graph:** Displays the code domain power for each symbol. Refer to *IQ Power Graph Display* on page 2-19.

- **Constellation:** Displays the signal as an I-Q constellation.
- **Mainview Content...:** Selects a view to display in the main view. You can select Code Domain Power, Power Codogram, or IQ Power Graph. Refer to *Scale and Format in the Main View* on page 2-15 for more information about the views.
- **Code Order...:** Sets the way that code channels are arranged on the display. You can select Hadamard or BitReverse.
- **Menu Off:** Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW:DEFINE** key.

## Pilot to Code Channel Measurement

**NOTE.** *To access the pilot to code channel measurement, you need to set the radio configuration setting to RC3/RC4 in the modulation accuracy measurement.*

The pilot to code channel measurement measures the time difference between the pilot channel and other code channels detected in the received signal. Figure 2-27 shows an example of the pilot to code channel measurement.




Figure 2-27: Pilot to code channel measurement-reverse link

<b>Display Elements</b>	<p>The following information is shown in the pilot to code channel measurement display:</p> <ul style="list-style-type: none"><li>■ <b>Overview:</b> This view can contain power versus time or spectrogram.</li><li>■ <b>Subview:</b> This view can contain spectrum, EVM, magnitude error, phase error, and constellation.</li><li>■ <b>Main view:</b> This view lists the following measurement results for the selected PCG:<ul style="list-style-type: none"><li>Power level</li><li>Timing referred to the pilot channel</li><li>Phase referred to the pilot channel</li><li>Code domain error</li></ul></li></ul>
	<p>The display content in the subview can be changed using the VIEW DEFINE menu. Refer to <i>Changing the View Contents</i> on page 2-48 for more information about the VIEW DEFINE menu.</p>

**Setting the Timing Parameters** You can set the following timing parameters using the TIMING menu. Press the **TIMING** key to open the TIMING menu.

- **Acquisition Length (chips):** Sets the acquisition length in chips. The range depends on the acquisition memory size and the span setting.
- **Acquisition Length (s):** Displays the acquisition length in seconds.
- **Acquisition History:** Specifies the number of the block to display and analyze. The latest block is number zero. Older blocks have larger negative numbers.
- **Analysis Interval:** Sets the analysis interval in chips. The range depends on the acquisition length setting.
- **Analysis Offset:** Sets the start point of the analysis with respect to the left end of the acquisition length in chips.
- **Spectrum Length:** Displays the time length for FFT processing of the spectrum displayed in the subview. This value is equivalent to one frame acquisition length.
- **Spectrum Offset:** Sets the beginning of Spectrum Length with respect to the left end of the acquisition length.

---

**NOTE.** Refer to the WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual for detailed information about the timing parameters.

## Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

- **Analyze:** Performs analysis for the time slots in the analysis range.
- **Radio Configuration...:** Select the radio configuration for the measurement. You can select only RC3/RC4.
- **Select PCG:** Sets the PCG (power control groups) for the measurement.
- **Limits...:** Sets the pass/fail limits for the pilot to code channel measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-51 for more information.
- **Scroll Table:** Scrolls the table displayed in the view.
- **Active Channel Threshold:** Sets the active channel threshold level (in dB from the pilot) used for deciding whether a code channel is active or inactive. You can set the value from -50 dB to 50 dB.
- **IQ Swap:** Sets whether to swap the I and Q data streams before demodulation.
- **Measurement Filter...:** Selects the measurement filter to apply when calculating pilot to code channel results. You can select None, cdma2000, or cdma2000+EQ (equalizer).
- **Walsh Code Length...:** Selects the Walsh code length. You can select Composite, 64, 32, 16, 8, 4, or 2. This setting is only available when Measurement Level is set to Symbol and Radio Configuration is set to RC3/RC4. When Radio Configuration is set to RC1/RC2, the Walsh code length is fixed at 64 and cannot be changed by the user.

**Changing the View Contents**

You can change the contents in the subview using the VIEW DEFINE menu. Press the **DEFINE** key to display the VIEW DEFINE menu.

- **Show Views:** Selects the view style on the screen. You can select Single or Multi.
- **Overview Content...:** Selects a view to display in the overview. You can select Spectrogram or Waveform (power versus time).
- **Subview Content...:** Selects a view to display in the subview:
  - **Spectrum:** Displays spectrum of the input signal.
  - **EVM:** Displays changes of EVM (Error Vector Magnitude) over time.
  - **MagErr:** Displays changes of magnitude error over time.
  - **PhaseErr:** Displays changes of phase error over time.
  - **Constellation:** Displays the signal as an I-Q constellation.
- **Menu Off:** Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW:DEFINE** key.

## Gated Output Power Measurement

The Gated Output power measurement measures the total RF power in a selected channel. Figure 2-28 shows an example of the gated output power measurement.




Figure 2-28: Gated output power measurement

### Display Elements

The following information is shown in the gated output power measurement display:

- **Overview:** This view can contain power versus time or spectrogram.
- **Subview:** This view can contain spectrum.
- **Main view:** This view can contain power versus time.

The display content in the overview can be changed using the VIEW DEFINE menu. Refer to *Changing the View Contents* on page 2-50 for more information about the VIEW DEFINE menu.

### Setting the Timing Parameters

You can set the following timing parameter using the TIMING menu. Press the **TIMING** key to open the TIMING menu.

- **Acquisition History:** Specifies the block number to be analyzed. Block number “0” corresponds to the latest block.

## Setting the Measurement Parameters

You can set the following measurement parameters using the MEAS SETUP menu. Press the **MEAS SETUP** key to open the MEAS SETUP menu.

In the MEAS SETUP menu, you can set the following parameters:

- **Analyze:** Performs analysis for the time slots in the analysis range.
- **Burst Sync...:** Sets the burst point to be measured. You can select Rising Edge, Mid Point, or Trigger Position.
- **Burst Offset:** Sets the burst offset between the trigger position and the burst position for the measurement. You can set the value from -1 ms to 1ms. This setting is only available when Burst Sync is set to Trigger Position.
- **Ref. Channel Select:** Selects the reference mode used to measure the power level. You can select Auto or Man (manual). For Auto, the reference level is measured from the input signal. For Man, you can set the reference level in the Ref. Channel Level menu item.
- **Ref. Channel Level:** Sets the reference level used to measure the power level. You can set the value from -150 dBm to 30 dBm. This setting is only available when Ref. Channel Select is set to Man (manual).
- **Limits...:** Sets the pass/fail limits for the gated output power measurement. When pressing this side key, the measurement limits editor appears. Refer to *Editing the Measurement Limits* on page 2-55 for more information.

## Changing the View Contents

You can change the contents in the overview using the VIEW DEFINE menu. Press the **DEFINE** key to display the VIEW DEFINE menu.

- **Show Views:** Sets the view style on the screen. You can select Single or Multi.
- **Overview Content...:** Selects a view to display in the overview. You can select Spectrogram or Waveform (power versus time).
- **Menu Off:** Hides the side menu. To display the menu again, press the **MENU** side key or **VIEW:DEFINE** key.

## Scale in the Main View

You can set the scale of the main view using the VIEW SCALE menu. Press the **SCALE** key to open the menu.

- **Auto Scale:** Sets the start value and the scale of the vertical axis to display the entire waveform.
- **Horizontal Scale:** Sets the scale of the horizontal axis.
- **Horizontal Start:** Sets the minimum (left) value of the horizontal axis.
- **Vertical Scale:** Sets the scale of the vertical axis.
- **Vertical Stop:** Sets the maximum (top) value of the vertical axis.
- **Full Scale:** Sets the scale of the vertical axis to the default full scale value.

# Editing the Measurement Limits

This section describes how to set measurement limits that can be used to perform pass/fail testing for the cdma2000 measurements.

Refer to *Measurement Limit Defaults* on page 2-61 for information about the default settings of each measurement limit.

## Using the Measurement Limits Editor

All of the measurement limits are set in the measurement limits editor, which you access from the **Limits...** side key on the MEAS SETUP menu.

Figure 2-29 shows the measurement limits editor for the cdma2000 forward link measurements.

Tektronix WCA 280A					03/12/01 10:42:17	PAUSE	LIMITS
Frequency: 1.5 GHz		Acquisition Length: 3.84 ms					Cancel - Back
Span: 5 MHz							Select row to edit
Input Att: 20 dB							Enable Limit
Limit	Enable	Lower	Upper	Units			No Yes
Channel Power	No	-150	30	dBm			Lower Limit (dBm)
ACPR		Select this row to edit limits					-150
Intermod 3rd Order	Yes		-45	dBc			Upper Limit (dBm)
Intermod 5th Order	Yes		-55	dBc			30
SEM Offset From Channel		Select this row to edit limits					Default all limits to...
SEM Inband Spurious		Select this row to edit limits					BC0
RMS EVM	No		10	percent			
Peak EVM	No		31	percent			
Peak Code Domain Error	No		0.4	dB			
Rho	Yes	0.912					
Pilot To Code Timing	Yes	-50n	50n	s			
Pilot To Code Phase	Yes	-0.15	0.15	radian			
OBW	Yes		1.48M	Hz			
Tau	Yes		0.00001	s			

Figure 2-29: Measurement limits editor

Table 2-1 describes all of the measurement limit items available in the measurement limits editor.

**Table 2-1: Measurement limits items**

Limit item	Description	Lower limit range	Upper limit range
Channel power	Sets the lower and upper limits for the Channel Power measurement.	-200 to 200 dBm	-200 to 200 dBm
ACPR	Select this item to access another measurement limits editor to edit ACPR limits.	Not settable	-200 to 200 dBc
Intermod 3rd Order	Sets the upper limit of the third harmonic distortion component for the Intermodulation measurement.	Not settable	-200 to 200 dBc
Intermod 5th Order	Sets the upper limit of the fifth harmonic distortion component for the Intermodulation measurement.	Not settable	-200 to 200 dBc
SEM Offset From Channel	Select this item to access another measurement limits editor to edit SEM offset from channel limits.	-----	-----
SEM Inband Spurious	Select this item to access another measurement limits editor to edit SEM Inband spurious limits.	-----	-----
RMS EVM	Sets the upper limit for the RMS EVM measurement.	Not settable	0 to 100%
Peak EVM	Sets the upper limit for the Peak EVM measurement.	Not settable	0 to 100%
Peak Code Domain Error	Sets the upper limit for the Peak code domain error measurement.	Not settable	-200 to 200 dB
Rho	Sets the lower limit of Rho for the modulation accuracy measurement.	0 to 1	Not settable
Pilot To Code Timing	Sets the upper limit for the pilot to code timing measurement.	Not settable	0 to 10 s
Pilot To Code Phase	Sets the lower and upper limits for the pilot to code phase measurement.	Not settable	0 to 100 degree
OBW	Sets the upper and lower limits for the OBW measurement.	0 to 30 MHz	0 to 30 MHz
Tau*	Sets the lower limit of Tau for the modulation accuracy measurement.	0 to 1 s	Not settable
Gated Output Power*	Select this item to access another measurement limits editor to edit gated output power limits.	-----	-----

\* These items are only available in the cdma2000 reverse link measurements.

## Setting a Measurement Limit

Perform the following procedure to set measurement limits:

1. Press the **MEAS SETUP** menu key to open the MEAS SETUP menu.
2. Press the **Limits...** side key to open the measurement limits editor with **LIMITS** menu.
3. Press the **Select row to edit** side key.
4. Turn the rotary knob or press the arrow keys to select the row that you want to edit.
5. Press the **Enable Limit** side key to enable or disable the pass/fail testing for the specified limit(s).
6. Press the **Lower Limit** side key to set the lower limit for the selected measurement item, if applicable.
7. Press the **Upper Limit** side key to set the upper limit for the selected measurement item.

When you want to set limits for the spectrum emission mask or gated output power measurement, perform the following steps to open another measurement limits editor:

1. Press the **Select row to edit** side key.
2. Turn the rotary knob or press the arrow keys to select **ACPR, SEM Offset From Channel, SEM Inband Spurious, or Gated Output Power** row.
3. Press the **Edit ACPR Limits..., Edit SEM Offset Limits..., Edit SEM Inband Limits..., or Edit Gated Output Power Limits...** (reverse link measurements only) side key. This opens the limits editor to set more complex limits for the ACPR, spectrum emission mask or gated output power measurement. Figure 2-31 shows the measurement limits editor for the ACPR measurement.

**Setting the ACPR Limits**

When you select the ACPR row in the measurement limits editor, another measurement limits editor for the ACPR measurement is displayed. Figure 2-30 shows the measurement limits editor for the ACPR measurement.




Figure 2-30: ACPR measurement limits editor

Table 2-2 lists the measurement limit items that can be set in the measurement limits editor.

Table 2-2: Measurement limit items for the ACPR measurement

Item	Description	Limit ranges
Enable	Enables or disables use of the limits in the specified zone (A to L).	-----
Frequency	Sets the frequency offset for the zone.	-3 to 3 GHz (WCA230A) -8 to 8 GHz (WCA280A)
Measurement BW	Sets the measurement bandwidth for the zone.	-3 to 3 GHz (WCA230A) -8 to 8 GHz (WCA280A)
Limit (Abs)	Sets a relative level limit.	-200 to 200 dBm
Limit (Rel)	Sets an absolute level limit.	-200 to 200 dBc

Table 2-2: Measurement limit items for the ACPR measurement (cont.)

Item	Description	Limit ranges
Fail Mode	Selects the fail mode to detect fail conditions between the measurement results and the test limits. The choices are: <ul style="list-style-type: none"> <li>■ Absolute: Fail is detected when the absolute measurement result is larger than the limit for Limit (Abs).</li> <li>■ Relative: Fail is detected when the relative measurement result is larger than the limit for Limit (Rel).</li> </ul>	-----

Perform the following steps to set measurement limits in the limits editor:

1. Press the **Select column to edit** side key.
2. Turn the rotary knob or press the arrow keys to select the column that you want to edit.
3. Press the **Enable** side key to enable or disable use of the limits for the zone.
4. Press the side key corresponding to the limit item, and then use the rotary knob or arrow keys to set the value.
5. Press the **Failure Mode...** side key to select the failure mode.
6. Press the **Default limits to...** side key if you want to use a given measurement limit for the measurement. Refer to *Measurement Limit Defaults* on page 2-61 for information about the default settings of each measurement limit.

## Setting the Spectrum Emission Mask Limits

When you select the SEM Offset From Channel or SEM Inband Spurious row in the measurement limits editor, another measurement limits editor for the spectrum emission mask measurement is displayed. Figure 2-31 shows the measurement limits editor for the spectrum emission mask measurement.




Figure 2-31: Spectrum emission mask measurement limits editor

Table 2-3 lists the measurement limit items that can be set in the measurement limits editor.

Table 2-3: Measurement limit items for the spectrum emission mask measurement

Item	Description	Limit ranges
Enable	Enables or disables use of the mask in the specified zone (A, B, C, D, or E).	-----
Beginning Frequency	Sets the beginning frequency for the zone.	-3 to 3 GHz (WCA230A) -8 to 8 GHz (WCA280A)
Ending Frequency	Sets the ending frequency for the zone.	-3 to 3 GHz (WCA230A) -8 to 8 GHz (WCA280A)
Measurement Bandwidth	Sets the measurement bandwidth.	-3 to 3 GHz (WCA230A) -8 to 8 GHz (WCA280A)
Offset from Carrier*	Specifies which offset side is to be measured You can select Upper (positive), Lower (negative), or Both.	-----

Table 2-3: Measurement limit items for the spectrum emission mask measurement (cont.)

Item	Description	Limit ranges
Fail if signal exceeds	Selects the fail mode to detect fail conditions between the measurement results and the test limits. The choices are: <ul style="list-style-type: none"> <li>■ Absolute: Fail is detected when one of the absolute measurement results is larger than the limit for Beginning Absolute Limit and/or Ending Absolute Limit.</li> <li>■ Relative: Fail is detected when one of the relative measurement results is larger than the limit for Beginning Relative Limit and/or Ending Relative Limit.</li> <li>■ Rel OR Abs: Fail is detected when one of the absolute measurement results is larger than the limit for Beginning Absolute Limit and Ending Absolute Limit OR one of the relative measurement results is larger than the limit for Beginning Relative Limit and Ending Relative Limit.</li> <li>■ Rel AND Abs: Fail is detected when one of the absolute measurement results is larger than the limit for Beginning Absolute Limit and Ending Absolute Limit AND one of the relative measurement results is larger than the limit for Beginning Relative Limit and Ending Relative Limit.</li> </ul>	-----
Beginning Absolute Limit	Sets an absolute level limit at Beginning Frequency.	-200 to 200 dBm
Ending Absolute Limit	Sets an absolute level limit at Ending Frequency.	-200 to 200 dBm
Beginning Relative Limit	Sets a relative level limit at Beginning Frequency.	-200 to 200 dBc
Ending Relative Limit	Sets a relative level limit at Ending Frequency.	-200 to 200 dBc

\* This item is only available when SEM Offset From Channel is selected..

Perform the following steps to set measurement limits in the limits editor:

1. Press the **Select column to edit** side key.
2. Turn the rotary knob or press the arrow keys to select the column that you want to edit.
3. Press the **Enable** side key to enable or disable use of the limits for the zone.
4. Press the side key corresponding to the limit item, and then use the rotary knob or arrow keys to set the value.
5. Press the **Default limits to...** side key if you want to use a given measurement limit for the measurement. Refer to *Measurement Limit Defaults* on page 2-61 for information about the default settings of each measurement limit.
6. When you press the **Rescale Graph** side key, the graph is rescaled to match the set limits.

### Setting the Gated Output Power Limits (Reverse Link Only)

When you select the Gated Output Power row in the measurement limits editor, another measurement limits editor for the gated output power measurement is displayed. Figure 2-32 shows the measurement limits editor for the gated output power measurement.




Figure 2-32: Gated output power measurement limits editor

Table 2-4 lists the measurement limit items that can be set in the measurement limits editor.

Table 2-4: Measurement limit items for the gated output power measurement

Item	Description	Limit ranges
Enable	Enables or disables use of the mask in the specified zone (A, B, C, D, or E).	-----
Beginning Time Offset	Sets the beginning time for the zone.	-10 to 10 s
Ending Time Offset	Sets the ending time for the zone.	-10 to 10 s
Limit Type	Sets the limit type for the measurement. You can select Upper or Lower.	-----
Offset Side	Specifies which offset side is to be measured. You can select Upper (positive), Lower (negative), or Both.	-----

Table 2-4: Measurement limit items for the gated output power measurement (cont.)

Item	Description	Limit ranges
Fail if signal exceeds	Selects the fail mode to detect fail conditions between the measurement results and the test limits. The choices are: <ul style="list-style-type: none"> <li>■ Absolute: Fail is detected when one of the absolute measurement results is larger than the limit for Beginning Absolute Limit and/or Ending Absolute Limit.</li> <li>■ Relative: Fail is detected when one of the relative measurement results is larger than the limit for Beginning Relative Limit and/or Ending Relative Limit.</li> <li>■ Rel OR Abs: Fail is detected when one of the absolute measurement results is larger than the limit for Beginning Absolute Limit and Ending Absolute Limit OR one of the relative measurement results is larger than the limit for Beginning Relative Limit and Ending Relative Limit.</li> <li>■ Rel AND Abs: Fail is detected when one of the absolute measurement results is larger than the limit for Beginning Absolute Limit and Ending Absolute Limit AND one of the relative measurement results is larger than the limit for Beginning Relative Limit and Ending Relative Limit.</li> </ul>	-----
Beginning Absolute Limit	Sets an absolute level limit at Beginning Time Offset.	-200 to 200 dBm
Ending Absolute Limit	Sets an absolute level limit at Ending Time Offset.	-200 to 200 dBm
Beginning Relative Limit	Sets a relative level limit at Beginning Time Offset.	-200 to 200 dB
Ending Relative Limit	Sets a relative level limit at Ending Time Offset.	-200 to 200 dB

Perform the following steps to set measurement limits in the limits editor:

1. Press the **Select column to edit** side key.
2. Turn the rotary knob or press the arrow keys to select the column that you want to edit.
3. Press the **Enable** side key to enable or disable use of the limits for the zone.
4. Press the side key corresponding to the limit item, and then use the rotary knob or arrow keys to set the value.
5. Press the **Default limits to...** side key if you want to use a given measurement limits for the measurement. Refer to *Measurement Limit Defaults* on page 2-61 for information about the default settings of each measurement limit.
6. When you press the **Rescale Graph** side key, the graph is rescaled to match the set limits.

## Saving and Loading Measurement Limits

Measurement limits that set in the measurement limits editor can be saved as a file and loaded from a file. This section describes how to save and load measurement limits.

Refer to the *WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual*, for further information about file operation including how to enter a file name and how to delete a file.

### Saving Measurement Limits

Perform the following steps to save the current measurement limits to a file:

1. When you open the spectrum emission mask measurement limits editor or gated output power measurement limits editor, press the **Cancel-Back (MENU)** side key to return the measurement limit editor (see Figure 2-29).
2. Press the **Save Limits** side key to open the **Save to File** menu.  
You can save the limits by using the preset file name or by entering a new file name.
3. To use the preset file name, press one of the following side keys: **Save to LimitsA**, **Save to LimitsB**, or **Save to LimitsC**.
4. To enter a new file name, type a file name in the text box at the top of the menu, and then press the **Save File Now** side key.

The file extension \*.lmt is automatically added to the limits file.

### Loading Measurement Limits

Perform the following steps to load measurement limits from a file:

1. When you open the spectrum emission mask measurement limits editor or gated output power measurement limits editor, press the **Cancel-Back (MENU)** side key to return the measurement limit editor (see Figure 2-29).
2. Press the **Load Limits** side key to open the **Load From File** menu.
3. To load limits from the preset file, press one of the following side keys: **Load from LimitsA**, **Load from LimitsB**, or **Load from LimitsC**.
4. To load limits from an existing file, select the file from the file list, and then press the **Load File Now** side key.

## Measurement Limit Defaults

Tables 2-5 through 2-21 list the default limit settings used to perform the pass/file testing for the cdma2000 measurements. Refer to *Using the Measurement Limits Editor* on page 2-51 for procedures to edit the measurement limits.

<b>Common Limits</b>	Tables 2-5 and 2-6 list the common measurement limits that can be used for the measurements other than the ACPR, Spectrum Emission Mask, and Gated Output Power measurements.
----------------------	---

**Table 2-5: Forward link common limits**

Limit	Enable	Lower	Upper	Units
Channel Power	No	-150	30	dBm
Intermod 3rd Order	Yes	N.A	-45	dBc
Intermod 5th Order	Yes	N.A	-55	dBc
RMS EVM	No	N.A	10	percent
Peak EVM	No	N.A	31	percent
Peak Code Domain Error	No	N.A	0.4	dB
Rho	Yes	0.912	N.A	N.A
Pilot To Code Timing	Yes	-50 n	50 n	s
Pilot To Code Phase	Yes	-0.15	0.15	radian
OBW	Yes	N.A	1.48 M	Hz
Tau	Yes	N.A	0.00001	s

**Table 2-6: Reverse link common limits**

Limit	Enable	Lower	Upper	Units
Channel Power	No	-150	30	dBm
Intermod 3rd Order	Yes	N.A	-42	dBc
Intermod 5th Order	Yes	N.A	-50	dBc
RMS EVM	No	N.A	10	percent
Peak EVM	No	N.A	24	percent
Peak Code Domain Error	No	N.A	0.25	dB
Rho	Yes	0.994	N.A	N.A
Pilot To Code Timing	Yes	-10 n	10 n	s
Pilot To Code Phase	Yes	-0.15	0.15	radian
OBW	Yes	N.A	1.48 M	Hz

**ACPR Limits** Tables 2-7 and 2-8 list the measurement limits that can be used for the ACPR measurement.

**Table 2-7: Forward link: all band classes**

Zone	Enable	Frequency	Measure BW	Limit (Abs)	Limit (Rel)	Fail Mode
A	Yes	750 kHz	30 kHz	-27 dBm	-45 dBc	Relative
B	Yes	-750 kHz	30 kHz	-27 dBm	-45 dBc	Relative
C	Yes	1.995 MHz	30 kHz	-27 dBm	-60 dBc	Relative
D	Yes	-1.995 MHz	30 kHz	-27 dBm	-60 dBc	Relative
E	Yes	3.125 MHz	30 kHz	-13 dBm	-60 dBc	Relative
F	No	-3.125 MHz	30 kHz	-13 dBm	-60 dBc	Relative
G	No	4 MHz	30 kHz	-13 dBm	-60 dBc	Relative
H	No	-4 MHz	30 kHz	-13 dBm	-60 dBc	Relative
I	No	7.5 MHz	30 kHz	-13 dBm	-60 dBc	Relative
J	No	-7.5 MHz	30 kHz	-13 dBm	-60 dBc	Relative
K	No	0 Hz	30 kHz	-13 dBm	-60 dBc	Relative
L	No	0 Hz	30 kHz	-13 dBm	-60 dBc	Relative

**Table 2-8: Reverse link: all band classes**

Zone	Enable	Frequency	Measure BW	Limit (Abs)	Limit (Rel)	Fail Mode
A	Yes	900 kHz	30 kHz	-27 dBm	-42 dBc	Relative
B	Yes	-900 kHz	30 kHz	-27 dBm	-42 dBc	Relative
C	Yes	1.995 MHz	30 kHz	-27 dBm	-54 dBc	Relative
D	Yes	-1.995 MHz	30 kHz	-27 dBm	-54 dBc	Relative
E	Yes	3.125 MHz	30 kHz	-13 dBm	-54 dBc	Relative
F	No	-3.125 MHz	30 kHz	-13 dBm	-54 dBc	Relative
G	No	4 MHz	30 kHz	-13 dBm	-54 dBc	Relative
H	No	-4 MHz	30 kHz	-13 dBm	-54 dBc	Relative
I	No	7.5 MHz	30 kHz	-13 dBm	-54 dBc	Relative
J	No	-7.5 MHz	30 kHz	-13 dBm	-54 dBc	Relative
K	No	0 Hz	30 kHz	-13 dBm	-54 dBc	Relative
L	No	0 Hz	30 kHz	-13 dBm	-54 dBc	Relative

**SEM Offset from Channel  
Limits**

Tables 2-9 through 2-17 list the measurement limits that can be used for the SEM Offset From Channel measurement.

**Table 2-9: Forward link: BC (band class) 0, 2, 3, 5, and 9**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	No	No
Start Frequency	750 kHz	1.98 MHz	4 MHz	4 MHz	20 MHz
Stop Frequency	1.98 MHz	4.00 MHz	20 MHz	3 GHz	8 GHz
Measurement BW	30 kHz	30 kHz	1 MHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Relative	Rel OR Abs	Absolute	Absolute	Absolute
Absolute Start	30 dBm	-27 dBm	-36 dBm	-13 dBm	-13 dBm
Absolute Stop	30 dBm	-27 dBm	-36 dBm	-13 dBm	-13 dBm
Relative Start	-45 dBc	-55 dBc	0 dBc	0 dBc	0 dBc
Relative Stop	-45 dBc	-55 dBc	0 dBc	0 dBc	0 dBc

**Table 2-10: Forward link: BC (band class) 1, 4, and 8**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	Yes	No
Start Frequency	885 kHz	1.25 MHz	2.25 MHz	4 MHz	4 MHz
Stop Frequency	1.25 MHz	2.25 MHz	4 MHz	20 MHz	3 GHz
Measurement BW	30 kHz	30 kHz	1 MHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Relative	Rel OR Abs	Absolute	Absolute	Absolute
Absolute Start	30 dBm	-9 dBm	-13 dBm	-36 dBm	-13 dBm
Absolute Stop	30 dBm	-9 dBm	-13 dBm	-36 dBm	-13 dBm
Relative Start	-45 dBc	-45 dBc	0 dBc	0 dBc	0 dBc
Relative Stop	-45 dBc	-45 dBc	0 dBc	0 dBc	0 dBc

**Table 2-11: Forward link: BC (band class) 3b**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	No	No
Start Frequency	750 kHz	1.98 MHz	4 MHz	4 MHz	20 MHz
Stop Frequency	1.98 MHz	4 MHz	20 MHz	3 MHz	8 GHz
Measurement BW	30 kHz	30 kHz	1 MHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Relative	Relative	Absolute	Absolute	Absolute
Absolute Start	30 dBm	-27 dBm	-36 dBm	-13 dBm	-13 dBm
Absolute Stop	30 dBm	-27 dBm	-36 dBm	-13 dBm	-13 dBm
Relative Start	-45 dBc	-60 dBc	0 dBc	0 dBc	0 dBc
Relative Stop	-45 dBc	-60 dBc	0 dBc	0 dBc	0 dBc

**Table 2-12: Forward link: BC (band class) 6**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	Yes	Yes
Start Frequency	885 kHz	1.25 MHz	1.45 MHz	2.25 MHz	4 MHz
Stop Frequency	1.25 MHz	1.45 MHz	2.25 MHz	4 MHz	20 MHz
Measurement BW	30 kHz	30 kHz	30 kHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Relative	Rel OR Abs	Rel OR Abs	Absolute	Absolute
Absolute Start	30 dBm	-13 dBm	-13 dBm	-13 dBm	-36 dBm
Absolute Stop	30 dBm	-13 dBm	-26.6 dBm <sup>1</sup>	-13 dBm	-36 dBm
Relative Start	-45 dBc	-45 dBc	-45 dBc	0 dBc	0 dBc
Relative Stop	-45 dBc	-45 dBc	-45 dBc	0 dBc	0 dBc

1 Based on  $-[13+17x(\Delta f-1.45 \text{ MHz})] \text{ dBm}$  when  $\Delta f$  is 2.25 MHz.

**Table 2-13: Forward link: BC (band class) 7**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	Yes	Yes
Start Frequency	750 kHz	1.98 MHz	3.25 MHz	4 MHz	4 MHz
Stop Frequency	1.98 MHz	3.25 MHz	4 MHz	20 MHz	20 MHz
Measurement BW	30 kHz	30 kHz	30 kHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Relative	Rel OR Abs	Rel OR Abs	Absolute	Absolute
Absolute Start	30 dBm	-27 dBm	-46 dBm	-36 dBm	-36 dBm
Absolute Stop	30 dBm	-27 dBm	-46 dBm	-36 dBm	-36 dBm
Relative Start	-45 dBc	-55 dBc	-55 dBc	0 dBc	0 dBc
Relative Stop	-45 dBc	-55 dBc	-55 dBc	0 dBc	0 dBc

**Table 2-14: Reverse link: BC (band class) 0, 2, 3, 5, and 9**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	No	No
Start Frequency	885 kHz	1.98 MHz	4 MHz	4 MHz	20 MHz
Stop Frequency	1.98 MHz	4 MHz	20 MHz	3 GHz	8 GHz
Measurement BW	30 kHz	30 kHz	1 MHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Rel AND Abs	Rel AND Abs	Absolute	Absolute	Absolute
Absolute Start	-54 dBm	-54 dBm	-36 dBm	-13 dBm	-13 dBm
Absolute Stop	-54 dBm	-54 dBm	-36 dBm	-13 dBm	-13 dBm
Relative Start	-42 dBc	-55 dBc	0 dBc	0 dBc	0 dBc
Relative Stop	-42 dBc	-55 dBc	0 dBc	0 dBc	0 dBc

**Table 2-15: Reverse link: BC (band class) 1, 4, and 8**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	No	No
Start Frequency	1.25 MHz	1.98 MHz	4 MHz	4 MHz	20 MHz
Stop Frequency	1.98 MHz	4 MHz	20 MHz	3 GHz	8 GHz
Measurement BW	30 kHz	30 kHz	1 MHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Relative	Rel OR Abs	Absolute	Absolute	Absolute
Absolute Start	-54 dBm	-54 dBm	-36 dBm	-13 dBm	-13 dBm
Absolute Stop	-54 dBm	-54 dBm	-36 dBm	-13 dBm	-13 dBm
Relative Start	-42 dBc	-50 dBc	0 dBc	0 dBc	0 dBc
Relative Stop	-42 dBc	-50 dBc	0 dBc	0 dBc	0 dBc

**Table 2-16: Reverse link: BC (band class) 6**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	No	No
Start Frequency	1.25 MHz	1.98 MHz	2.25 MHz	2.25 MHz	4 MHz
Stop Frequency	1.98 MHz	2.25 MHz	4 MHz	4 MHz	20 MHz
Measurement BW	30 kHz	30 kHz	1 MHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Rel AND Abs	Rel OR Abs	Rel OR Abs	Absolute	Absolute
Absolute Start	-54 dBm	-54 dBm	-13 dBm	-13 dBm	-36 dBm
Absolute Stop	-54 dBm	-54 dBm	-14.75 dBm <sup>2</sup>	-13 dBm	-36 dBm
Relative Start	-42 dBc	-50 dBc	-45 dBc	0 dBc	0 dBc
Relative Stop	-42 dBc	-50 dBc	-45 dBc	0 dBc	0 dBc

2 Based on  $-[13+1x(\Delta f-2.25 \text{ MHz})] \text{ dBm}$  when  $\Delta f$  is 4 MHz.

**Table 2-17: Reverse link: BC (band class) 7**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	Yes	Yes
Start Frequency	885 kHz	1.98 MHz	2.25 MHz	4 MHz	4 MHz
Stop Frequency	1.98 MHz	2.25 MHz	4 MHz	20 MHz	20 MHz
Measurement BW	30 kHz	30 kHz	30 kHz	1 MHz	1 MHz
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Rel AND Abs	Rel AND Abs	Rel AND Abs	Absolute	Absolute
Absolute Start	-54 dBm	-54 dBm	-35 dBm	-36 dBm	-36 dBm
Absolute Stop	-54 dBm	-54 dBm	-35 dBm	-36 dBm	-36 dBm
Relative Start	-42 dBc	-54 dBc	-55 dBc	0 dBc	0 dBc
Relative Stop	-42 dBc	-54 dBc	-55 dBc	0 dBc	0 dBc

**SEM Inband Spurious  
Limits**

Tables 2-18 through 2-20 list the measurement limits that can be used for the SEM Inband Spurious measurement.

**Table 2-18: Forward and reverse link: BC (band class) 0, 1, 2, 3, 4, 5, 7, 8, and 9**

Zone	A	B	C	D	E
Enable	Yes	Yes	No	No	No
Start Frequency	1 GHz	925 MHz	935 MHz	1.805 GHz	4 MHz
Stop Frequency	3 GHz	935 MHz	960 MHz	1.880 GHz	8 GHz
Measurement BW	1 MHz	100 kHz	100 kHz	100 kHz	1 MHz
Failure Mode	Absolute	Absolute	Absolute	Absolute	Absolute
Absolute Start	-36 dBm	-67 dBm	-79 dBm	-71 dBm	-36 dBm
Absolute Stop	-36 dBm	-67 dBm	-79 dBm	-71 dBm	-36 dBm
Relative Start	0 dBc	0 dBc	0 dBc	0 dBc	0 dBc
Relative Stop	0 dBc	0 dBc	0 dBc	0 dBc	0 dBc

**Table 2-19: Forward link: BC (band class) 6**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	Yes	No
Start Frequency	1.8935 GHz	925 MHz	935 MHz	1.805 GHz	4 MHz
Stop Frequency	1.9196 GHz	935 MHz	960 MHz	1.880 GHz	20 MHz
Measurement BW	300 kHz	100 kHz	100 kHz	100 kHz	1 MHz
Failure Mode	Absolute	Absolute	Absolute	Absolute	Absolute
Absolute Start	-41 dBm	-67 dBm	-79 dBm	-71 dBm	-36 dBm
Absolute Stop	-41 dBm	-67 dBm	-79 dBm	-71 dBm	-36 dBm
Relative Start	0 dBc	0 dBc	0 dBc	0 dBc	0 dBc
Relative Stop	0 dBc	0 dBc	0 dBc	0 dBc	0 dBc

**Table 2-20: Reverse link: BC (band class) 6**

Zone	A	B	C	D	E
Enable	Yes	Yes	Yes	Yes	Yes
Start Frequency	1.8935 GHz	876 MHz	921 MHz	1.710 GHz	1.805 GHz
Stop Frequency	1.9196 GHz	915 MHz	960 MHz	1.785 GHz	1.880 GHz
Measurement BW	300 kHz	100 kHz	100 kHz	100 kHz	100 kHz
Failure Mode	Absolute	Absolute	Absolute	Absolute	Absolute
Absolute Start	-41 dBm	-98 dBm	-57 dBm	-98 dBm	-47 dBm
Absolute Stop	-41 dBm	-98 dBm	-57 dBm	-98 dBm	-47 dBm
Relative Start	0 dBc	0 dBc	0 dBc	0 dBc	0 dBc
Relative Stop	0 dBc	0 dBc	0 dBc	0 dBc	0 dBc

**Gated Output Power Limits**

Table 2-21 list the measurement limits that can be used for the gated output power measurement.

Table 2-21: Reverse link: all band classes

Zone	A	B	C	D	E
Enable	Yes	Yes	No	No	No
Start Time	0 s	630.5 µs	0 s	1.2555 ms	0 s
Stop Time	623.5 µs	3.125 ms	1.2485 ms	3.125 ms	3.125 ms
Upper/Lower	Lower	Upper	Lower	Upper	Upper
Offset Side	Both	Both	Both	Both	Both
Failure Mode	Relative	Relative	Relative	Relative	Absolute
Absolute Start	-150 dBm	30 dBm	-150 dBm	30 dBm	30 dBm
Absolute Stop	-150 dBm	30 dBm	-150 dBm	30 dBm	30 dBm
Relative Start	-3 dB	-20 dB	-3 dB	-20 dB	-150 dB
Relative Stop	-3 dB	-20 dB	-3 dB	-20 dB	-150 dB



# Syntax and Commands



# Command Groups

This section shows the organization of the Option 25 commands in a number of functional groups.

For detailed information about other commands can be used with the WCA230A or WCA280A, refer to the *WCA230A & WCA280A Wireless Communication Analyzers Programmer Manual*.

Items followed by question marks are queries; items without question marks are commands. Some items in this section have a question mark in parentheses (?) in the command header section; this indicates that the item can be both a command and a query.

You need to select one of the following measurement modes before executing any commands for the Option 25. To set the measurement mode, use the :INSTrument[:SElect] command using one of the mnemonics listed below:

**Table 3-1: Measurement modes**

Mnemonic	Meaning
DEMFLCDMA2K	cdma2000 forward link analysis
DEMRLCDMA2K	cdma2000 reverse link analysis

For more information on SCPI commands and programming structure, refer to *WCA230A & WCA280A Wireless Communication Analyzers Programmer Manual*.

---

**NOTE.** Throughout the header descriptions in this section, the word **Standard** in italics is substituted for either of the following two measurement standards; **FLCDMA2K** (cdma2000 forward link) or **RLCDMA2K** (cdma2000 reverse link).

---

## :CONFigure Commands

Use these commands to set up the analyzer to perform the specified measurement.

Table 3-2: :CONFigure commands

Header	Description
:CONFigure: <i>Standard</i> :ACPower	Sets up the analyzer to the ACPR measurement default settings.
:CONFigure: <i>Standard</i> :CCDF	Sets up the analyzer to the CCDF measurement default settings.
:CONFigure: <i>Standard</i> :CDPower	Sets up the analyzer to the code domain power measurement default settings.
:CONFigure: <i>Standard</i> :CHPower	Sets up the analyzer to the channel power measurement default settings.
:CONFigure: <i>Standard</i> :IM	Sets up the analyzer to the intermodulation measurement default settings.
:CONFigure: <i>Standard</i> :MACCuracy	Sets up the analyzer to the modulation accuracy measurement default settings.
:CONFigure: <i>Standard</i> :OBWidth	Sets up the analyzer to the occupied band width measurement default settings.
:CONFigure: <i>Standard</i> :PCCChannel	Sets up the analyzer to the pilot to code channel measurement default settings.
:CONFigure:RLCDMA2K:PVTIme	Sets up the analyzer to the gated output power measurement default settings.
:CONFigure: <i>Standard</i> :SEMask	Sets up the analyzer to the spectrum emission mask measurement default settings.

## :DISPlay Commands

Use these commands to control how to show measurement data on the screen.

Table 3-3: :DISPlay commands

Header	Description
<b>:DISPlay:<i>Standard</i>:CCDF subgroup</b>	
:DISPlay: <i>Standard</i> :CCDF:LINE:GAUSSian [:STATe] (?)	Sets whether to display the Gaussian line on the CCDF view.
:DISPlay: <i>Standard</i> :CCDF:LINE:REFerence [:STATe] (?)	Sets whether to display the reference line on the CCDF view.
:DISPlay: <i>Standard</i> :CCDF:LINE:REFerence:STORe	Stores a new reference line.
:DISPlay: <i>Standard</i> :CCDF:X[:SCALe]:AUTO (?)	Determines whether to set the horizontal scale automatically in the CCDF view.
:DISPlay: <i>Standard</i> :CCDF:X[:SCALe] :MAXimum (?)	Sets the horizontal maximum value (right end) in the CCDF view.
:DISPlay: <i>Standard</i> :CCDF:X[:SCALe] :OFFSet (?)	Sets the minimum horizontal value (left end) in the CCDF view.
:DISPlay: <i>Standard</i> :CCDF:Y[:SCALe]:FIT	Runs auto-scale on the CCDF view.
:DISPlay: <i>Standard</i> :CCDF:Y[:SCALe]:FULL	Sets the vertical axis to the default full-scale value in the CCDF view.
:DISPlay: <i>Standard</i> :CCDF:Y[:SCALe] :MAXimum (?)	Sets the maximum vertical value (top end) in the CCDF view.
:DISPlay: <i>Standard</i> :CCDF:Y[:SCALe] :MINimum (?)	Sets the minimum vertical value (bottom end) in the CCDF view.

Table 3-3: :DISPlay commands (cont.)

Header	Description
<b>:DISPlay:<i>Standard</i>:DDEMod subgroup</b>	
:DISPlay: <i>Standard</i> :DDEMod:MVlew:CORDer (?)	Sets the code order.
:DISPlay: <i>Standard</i> :DDEMod:MVlew:FORMAT (?)	Selects the main view display format.
:DISPlay: <i>Standard</i> :DDEMod:MVlew:X[:SCALE] :OFFSet (?)	Sets the minimum horizontal value (left end) in the main view.
:DISPlay: <i>Standard</i> :DDEMod:MVlew:X[:SCALE] :RANGE (?)	Sets the horizontal full-scale value in the main view.
:DISPlay: <i>Standard</i> :DDEMod:MVlew:Y[:SCALE]:FIT	Runs auto-scale on the main view.
:DISPlay: <i>Standard</i> :DDEMod:MVlew:Y[:SCALE] :FULL	Sets the main view's vertical axis to the default full-scale value.
:DISPlay: <i>Standard</i> :DDEMod:MVlew:Y[:SCALE] :OFFSet (?)	Sets the minimum vertical value (bottom end) in the main view.
:DISPlay: <i>Standard</i> :DDEMod:MVlew:Y[:SCALE] :PUnit (?)	Sets the unit of the vertical axis in the main view.
:DISPlay: <i>Standard</i> :DDEMod:MVlew:Y[:SCALE] :RANGE (?)	Sets the vertical full-scale value in the main view.
:DISPlay: <i>Standard</i> :DDEMod:SVlew:FORMAT (?)	Selects the subview display format.
:DISPlay: <i>Standard</i> :DDEMod:SVlew:X[:SCALE] :OFFSet (?)	Sets the minimum horizontal value (left end) in the subview.
:DISPlay: <i>Standard</i> :DDEMod:SVlew:X[:SCALE] :RANGE (?)	Sets the horizontal full-scale value in the subview.
:DISPlay: <i>Standard</i> :DDEMod:SVlew:Y[:SCALE]:FIT	Runs auto-scale on the subview.
:DISPlay: <i>Standard</i> :DDEMod:SVlew:Y[:SCALE] :FULL	Sets the subview's vertical axis to the default full-scale value.
:DISPlay: <i>Standard</i> :DDEMod:SVlew:Y[:SCALE] :OFFSet (?)	Sets the minimum vertical value (bottom end) in the subview.
:DISPlay: <i>Standard</i> :DDEMod:SVlew:Y[:SCALE] :RANGE (?)	Sets the vertical full-scale value in the subview.
<b>:DISPlay:<i>Standard</i>:SPECtrum subgroup</b>	
:DISPlay: <i>Standard</i> :SPECtrum:X[:SCALE] :OFFSet (?)	Sets the minimum horizontal value (left end) in the spectrum view.
:DISPlay: <i>Standard</i> :SPECtrum:X[:SCALE] :PDIVision (?)	Sets the horizontal scale in the spectrum view.
:DISPlay: <i>Standard</i> :SPECtrum:Y[:SCALE]:FIT	Runs auto-scale on the spectrum view.
:DISPlay: <i>Standard</i> :SPECtrum:Y[:SCALE]:FULL	Sets the vertical axis to the default full-scale value.
:DISPlay: <i>Standard</i> :SPECtrum:Y[:SCALE] :OFFSet (?)	Sets the minimum vertical value (bottom end) in the spectrum view.
:DISPlay: <i>Standard</i> :SPECtrum:Y[:SCALE] :PDIVision (?)	Sets the vertical scale in the spectrum view.

**Table 3-3: :DISPlay commands (cont.)**

Header	Description
<b>:DISPlay:RLCDMA2K:WAVeform subgroup</b>	
:DISPlay:RLCDMA2K:WAVeform:X[:SCALE]	Sets the minimum horizontal value in the time domain display.
:OFFSet (?)	
:DISPlay:RLCDMA2K:WAVeform:X[:SCALE]	Sets the horizontal or time scale per division in the spectrum view.
:PDIVision (?)	
:DISPlay:RLCDMA2K:WAVeform:Y[:SCALE]:FIT	Runs auto-scale on the time domain display.
:DISPlay:RLCDMA2K:WAVeform:Y[:SCALE]:FULL	Sets the vertical axis to the default full scale.
:DISPlay:RLCDMA2K:WAVeform:Y[:SCALE]	Sets the minimum vertical value in the time domain display.
:OFFSet (?)	
:DISPlay:RLCDMA2K:WAVeform:Y[:SCALE]	Sets the vertical scale per division in the time domain display.
:PDIVision (?)	

## :FETCh Commands

Use these commands to retrieve the measurement from the data taken by the latest :INITiate command.

If you want to perform a FETCh operation on fresh data, use the :READ commands, which acquire a new input signal and fetch the measurement results from that data.

**Table 3-4: :FETCh commands**

Header	Description
:FETCh:Standard:ACPower?	Returns the ACPR measurement results.
:FETCh:Standard:CCDF?	Returns the CCDF measurement results.
:FETCh:Standard:CDPower?	Returns the code domain power measurement results.
:FETCh:Standard:CHPower?	Returns the channel power measurement results.
:FETCh:Standard:IM?	Returns the intermodulation measurement results.
:FETCh:Standard:MACCuracy?	Returns the modulation accuracy measurement results.
:FETCh:Standard:OBWidth?	Returns the occupied bandwidth measurement results.
:FETCh:Standard:PCChannel?	Returns the pilot-to-code channel measurement results.
:FETCh:RLCDMA2K:PVTIME?	Returns the gated output power measurement results.
:FETCh:Standard:SEMask?	Returns the spectrum emission mask measurement results.
:FETCh:Standard:DISTribution:CCDF?	Returns the distribution data of the CCDF measurement.
:FETCh:RLCDMA2K:TAMPplitude:PVTIME?	Returns the time amplitude for the gated output power measurement.
:FETCh:Standard:SPECtrum:ACPower?	Returns the spectrum waveform data of the ACPR measurement.
:FETCh:Standard:SPECtrum:CHPower?	Returns the spectrum waveform data of the channel power measurement.
:FETCh:Standard:SPECtrum:IM?	Returns the spectrum waveform data of the intermodulation measurement.
:FETCh:Standard:SPECtrum:OBWidth?	Returns the spectrum waveform data of the occupied bandwidth measurement.

## :MMEMory Commands

Use these commands to manipulate files on the hard disk or floppy disk.

**Table 3-5: :MMEMory commands**

Header	Description
:MMEMory:LOAD:LIMit	Loads the limit from the specified file.
:MMEMory:STORe:LIMit	Stores the limit in the specified file.
:MMEMory:STORe:STABle	Stores the symbol table in the specified file.

## :READ Commands

Use these commands to acquire an input signal once in the single mode and obtain the measurement results from that data.

If you want to fetch the measurement results from the data currently residing in the memory without acquiring the input signal, use the :FETCH command.

**Table 3-6: :READ commands**

Header	Description
:READ: <i>Standard</i> :ACPower?	Returns the ACPR measurement results.
:READ: <i>Standard</i> :CCDF?	Returns the CCDF measurement results.
:READ: <i>Standard</i> :CHPower?	Returns the channel power measurement results.
:READ: <i>Standard</i> :IM?	Returns the intermodulation measurement results.
:READ: <i>Standard</i> :OBWidth?	Returns the occupied bandwidth measurement results.
:READ:RLCDMA2K:PVTIME?	Returns the gated output power measurement results.
:READ: <i>Standard</i> :SEMask?	Returns the spectrum emission mask measurement results.
:READ: <i>Standard</i> :DISTribution:CCDF?	Returns the distribution data of the CCDF measurement.
:READ:RLCDMA2K:TAMplitude:PVTIME?	Returns the time amplitude for the gated output power measurement.
:READ: <i>Standard</i> :SPECtrum:ACPower?	Returns the spectrum waveform data of the ACPR measurement.
:READ: <i>Standard</i> :SPECtrum:CHPower?	Returns the spectrum waveform data of the channel power measurement.
:READ: <i>Standard</i> :SPECtrum:IM?	Returns the spectrum waveform data of the intermodulation measurement.
:READ: <i>Standard</i> :SPECtrum:OBWidth?	Returns the spectrum waveform data of the occupied bandwidth measurement.

## :SENSe Commands

Use these commands to set the detailed measurement conditions.

Table 3-7: :SENSe commands

Header	Description
<b>[:SENSe]:Standard subgroup</b>	
[:SENSe]:Standard:ACQuisition:CHIPs (?)	Sets the acquisition length in chips.
[:SENSe]:Standard:ACQuisition:HISTory (?)	Sets the acquisition history.
[:SENSe]:Standard:ACQuisition:SEConds (?)	Sets the acquisition length in seconds.
[:SENSe]:Standard:ANALysis:INTerval (?)	Sets the analysis interval.
[:SENSe]:Standard:ANALysis:OFFSet (?)	Sets the analysis offset.
[:SENSe]:Standard:BLOCK (?)	Sets the number of the block to be measured.
[:SENSe]:Standard:[IMM]mediate	Starts the calculation for the acquired data.
[:SENSe]:Standard:MEASurement (?)	Selects the measurement item.
[:SENSe]:Standard:SPECTrum:OFFSet (?)	Sets the spectrum offset within the time window.
[:SENSe]:Standard:SPECTrum:TINTerval?	Returns the length of the time-domain information used to construct the spectrum trace.
<b>[:SENSe]:Standard:ACPower subgroup</b>	
[:SENSe]:Standard:ACPower:BANDwidth BWIDth:INTegration (?)	Sets the bandwidth of the main channel for the ACPR measurement.
[:SENSe]:Standard:ACPower:FILTer:COEFFicient (?)	Sets the filter roll-off rate for the ACPR measurement.
[:SENSe]:Standard:ACPower:FILTer:TYPE (?)	Sets the filter for the ACPR measurement.
[:SENSe]:Standard:ACPower:LIMit:ADJacent[1] 2 3.. 12:STATE (?)	Sets whether to enable or disable the adjacent limit testing for the ACPR measurement.
<b>[:SENSe]:Standard:CCDF subgroup</b>	
[:SENSe]:Standard:CCDF:RMEasurement	Clears the CCDF accumulator and restarts the measurement.
[:SENSe]:Standard:CCDF:THreshold (?)	Sets the threshold for the CCDF measurement.
<b>[:SENSe]:Standard:CDPower subgroup</b>	
[:SENSe]:Standard:CDPower:ACCThreshold (?)	Sets the active channel threshold level for the code domain power measurement.
[:SENSe]:Standard:CDPower:FILTer:MEASurement (?)	Selects the measurement filter for the code domain power measurement.
[:SENSe]:Standard:CDPower:IQSswap (?)	Sets whether to enable or disable IQ swapping for the code domain power measurement.
[:SENSe]:Standard:CDPower:MLEvel (?)	Selects the measurement level for the code domain power measurement.
[:SENSe]:FLCDMA2K:CDPower:PNOFFset (?)	Sets the PN offset for the code domain power measurement.
[:SENSe]:FLCDMA2K:CDPower:QOF (?)	Sets the quasi-orthogonal function for the code domain power measurement.
[:SENSe]:Standard:CDPower:SELect:CODE (?)	Sets the code in the halfslot for the code domain power measurement.
[:SENSe]:Standard:CDPower:SELect:PCG (?)	Sets the PCG for the code domain power measurement.
[:SENSe]:Standard:CDPower:WCODe (?)	Sets the Walsh code length for the code domain power measurement.

Table 3-7: :SENSe commands (cont.)

Header	Description
<b>[:SENSe]:Standard:CHPower subgroup</b>	
[:SENSe]:Standard:CHPower:BANDwidth BWIDth :INTegration (?)	Sets the channel bandwidth for the channel power measurement.
[:SENSe]:Standard:CHPower:FILTter:COEFFicient (?)	Sets the filter roll-off rate for the channel power measurement.
[:SENSe]:Standard:CHPower:FILTter:TYPE (?)	Selects the filter for the channel power measurement.
[:SENSe]:Standard:CHPower:LIMit[:STATE] (?)	Sets whether to enable or disable the limit testing for the channel power measurement.
<b>[:SENSe]:Standard:IM subgroup</b>	
[:SENSe]:Standard:IM:BANDwidth BWIDth :INTegration (?)	Sets the bandwidth of the main channel for the intermodulation measurement.
[:SENSe]:Standard:IM:FILTter:COEFFicient (?)	Sets the filter roll-off rate for the intermodulation measurement.
[:SENSe]:Standard:IM:FILTter:TYPE (?)	Selects the filter for the intermodulation measurement.
[:SENSe]:Standard:IM:LIMit:FORDer[:STATE] (?)	Sets whether to enable or disable the fifth order limit testing for the intermodulation measurement.
[:SENSe]:Standard:IM:LIMit:TORDer[:STATE] (?)	Sets whether to enable or disable the third order limit testing for the intermodulation measurement.
[:SENSe]:Standard:IM:SCOFFset (?)	Sets the frequency of the second channel for the intermodulation accuracy.
<b>[:SENSe]:Standard:MACCuracy subgroup</b>	
[:SENSe]:Standard:MACCuracy:ACCThreshold (?)	Sets the level (in dB from the pilot) which should be used when deciding whether a code channel is active or inactive for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:FILTter :MEASurement (?)	Selects the measurement filter for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:IQSswap (?)	Sets whether to enable or disable IQ swapping for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:LIMit:EVM:PEAK [:STATE] (?)	Sets whether to enable or disable the Peak EVM limit testing for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:LIMit:EVM:RMS [:STATE] (?)	Sets whether to enable or disable the RMS EVM limit testing for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:LIMit:PCDerror [:STATE] (?)	Sets whether to enable or disable the Peak Code Domain Error limit testing for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:LIMit:RHO [:STATE] (?)	Sets whether to enable or disable the Rho limit testing for the modulation accuracy measurement.
[:SENSe]:FLCDMA2K:MACCuracy:LIMit:TAU [:STATE] (?)	Sets whether to enable or disable the Tau limit testing for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:MLEvel (?)	Selects the measurement level for the modulation accuracy measurement.
[:SENSe]:FLCDMA2K:MACCuracy:PNOFFset (?)	Sets the PN offset for the modulation accuracy measurement.
[:SENSe]:FLCDMA2K:MACCuracy:QOF (?)	Sets the quasi-orthogonal function for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:RConfig (?)	Sets the radio configuration for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:SElect:CODE (?)	Sets the code in the halfslot for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:SElect:PCG (?)	Sets the PCG for the modulation accuracy measurement.
[:SENSe]:Standard:MACCuracy:WCODE (?)	Sets the Walsh code length for the modulation accuracy measurement.

Table 3-7: :SENSe commands (cont.)

Header	Description
<b>[:SENSe]:Standard:OBWidth subgroup</b>	
[:SENSe]:Standard:OBWidth:LIMIT[:STATe] (?)	Sets whether to enable or disable the limit testing for the occupied bandwidth measurement.
[:SENSe]:Standard:OBWidth:PERcent (?)	Sets the occupied bandwidth for the occupied bandwidth measurement.
<b>[:SENSe]:Standard:PCCHannel subgroup</b>	
[:SENSe]:Standard:PCCHannel:ACCThreshold (?)	Sets the level (in dB from the pilot) that should be used when deciding whether a code channel is active or inactive for the pilot to code channel measurement.
[:SENSe]:Standard:PCCHannel:FILTer :MEASurement (?)	Selects the measurement filter for the pilot to code channel measurement.
[:SENSe]:Standard:PCCHannel:IQSswap (?)	Sets whether to enable or disable IQ swapping for the pilot to code channel measurement.
[:SENSe]:Standard:PCCHannel:LIMit:PHASE [:STATe] (?)	Sets whether to enable or disable the phase limit testing for the pilot to code channel measurement.
[:SENSe]:Standard:PCCHannel:LIMit:TIME [:STATe] (?)	Sets whether to enable or disable the time limit testing for the pilot to code channel measurement.
[:SENSe]:RLCDMA2K:PCCHannel:PNOFFset (?)	Sets the PN offset for the pilot to code channel measurement.
[:SENSe]:Standard:PCCHannel:RCONfig (?)	Sets the radio configuration for the pilot to code channel measurement.
[:SENSe]:Standard:PCCHannel:SELect:CODE (?)	Sets the code in the halfslot for the pilot to code channel measurement.
[:SENSe]:Standard:PCCHannel:SELect:PCG (?)	Sets the PCG for the pilot to code channel measurement.
[:SENSe]:Standard:PCCHannel:WCode (?)	Sets the Walsh code length for the pilot to code channel measurement.
<b>[:SENSe]:RLCDMA2K:PVTIme subgroup</b>	
[:SENSe]:RLCDMA2K:PVTIme:BURSt:GATE (?)	Sets the burst gate for the power versus time measurement.
[:SENSe]:RLCDMA2K:PVTIme:BURSt:OFFSet (?)	Selects the burst offset between the trigger position and burst position for the power versus time measurement.
[:SENSe]:RLCDMA2K:PVTIme:BURSt:SYNC (?)	Selects the burst sync for the power versus time measurement.
[:SENSe]:RLCDMA2K:PVTIme:LIMit :ZONE[1 2 3 4 5]:STATe (?)	Sets whether to enable or disable the zone limit testing for the power versus time measurement.
[:SENSe]:RLCDMA2K:PVTIme:RCHannel :LEVel (?)	Sets the reference channel level for measuring the power level in dB.
[:SENSe]:RLCDMA2K:PVTIme:RCHannel :MODE (?)	Selects the reference channel level mode for measuring the power level in dB.
<b>[:SENSe]:Standard:SEMask subgroup</b>	
[:SENSe]:Standard:SEMask:BANDwidth BWIDth :INTegration (?)	Sets the channel bandwidth for the spectrum emission mask measurement.
[:SENSe]:Standard:SEMask:BURSt:OFFSet (?)	Sets the burst offset between the trigger position and burst point for the spectrum emission mask measurement.
[:SENSe]:Standard:SEMask:BURSt:SYNC (?)	Sets the burst sync for the spectrum emission mask measurement.
[:SENSe]:Standard:SEMask:FILTer:COEFFicient (?)	Sets the filter roll-off rate for the spectrum emission mask measurement.
[:SENSe]:Standard:SEMask:FILTer:TYPE (?)	Selects the filter for the spectrum emission mask measurement.
[:SENSe]:Standard:SEMask:LIMit:ISPurious :ZONE[1 2 3 4 5]:STATe (?)	Sets whether to enable or disable the inband spurious zone limit testing for the spectrum emission mask measurement.
[:SENSe]:Standard:SEMask:LIMit:OFCHannel :ZONE[1 2 3 4 5]:STATe (?)	Sets whether to enable or disable the offset from the channel zone limit testing for the spectrum emission mask measurement.

Table 3-7: :SENSe commands (cont.)

Header	Description
<code>[:SENSe]:Standard:SEMask:MEASurement (?)</code>	Selects the limit table type.
<code>[:SENSe]:Standard:SEMask:RCHannel:LEVel (?)</code>	Sets the reference channel level for measuring the spurious emission level.
<code>[:SENSe]:Standard:SEMask:RCHannel:MODE (?)</code>	Selects the reference channel level mode for measuring the spurious emission level.
<code>[:SENSe]:Standard:SEMask:SLOT:GATE (?)</code>	Sets the slot gate time for the spectrum mask measurement.

## Command Groups

# :CONFigure Commands

The :CONFigure commands set up the analyzer to the default settings for the specified measurement under the cdma2000 forward link or reverse link standard.

---

**NOTE.** Throughout the header descriptions in this section, the word **Standard** in *italics* is substituted for either of the following two measurement standards; **FLCDMA2K** (cdma2000 forward link) or **RLCDMA2K** (cdma2000 reverse link).

---

## Command Tree

```
:CONFi gure
  :FLCDMA2K|RLCDMA2K
    :ACPower
    :CCDF
    :CDPower
    :CHPower
    :IM
    :MACCuracy
    :OBWi dth
    :PCCHannel
    :PVTi me
    :SEMask
```

### :CONFigure:*Standard*:ACPower

Sets up the analyzer to the default settings for the ACPR measurement under the cdma2000 forward link or reverse link standard.

**Syntax**    :CONFi gure:FLCDMA2K|RLCDMA2K:ACPower

**Arguments**    None

**Measurement Modes**    DEMFLCDMA2K, DEMRLCDMA2K

**Examples**    :CONFi gure:FLCDMA2K:ACPower  
sets up the analyzer to the default settings for the ACPR measurement under the cdma2000 forward link standard.

**Related Commands**    :INSTRument[:SELect]

## :CONFigure:*Standard*:CCDF

Sets up the analyzer to the default settings for the CCDF measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : CONFi gure: FLCDMA2K | RLCDMA2K: CCDF

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : CONFi gure: FLCDMA2K: CCDF

sets up the analyzer to the default settings for the CCDF measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument [: SELect]

## :CONFigure:*Standard*:CDPower

Sets up the analyzer to the default settings for the code domain power measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : CONFi gure: FLCDMA2K | RLCDMA2K: CDPower

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : CONFi gure: FLCDMA2K: CDPower

sets up the analyzer to the default settings for the code domain power measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument [: SELect]

## :CONFigure:*Standard*:CHPower

Sets up the analyzer to the default settings for the channel power measurement under the cdma2000 forward link or reverse link standard.

**Syntax** :CONFi gure:FLCDMA2K|RLCDMA2K:CHPower

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :CONFi gure:FLCDMA2K:CHPower

sets up the analyzer to the default settings for the channel power measurement under the cdma2000 forward link standard.

**Related Commands** :INSTrument[:SElect]

## :CONFigure:*Standard*:IM

Sets up the analyzer to the default settings for the intermodulation measurement under the cdma2000 forward link or reverse link standard.

**Syntax** :CONFi gure:FLCDMA2K|RLCDMA2K:IM

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :CONFi gure:FLCDMA2K:IM

sets up the analyzer to the default settings for the intermodulation measurement under the cdma2000 forward link standard.

**Related Commands** :INSTrument[:SElect]

## :CONFigure:*Standard*:MACCuracy

Sets up the analyzer to the default settings for the modulation accuracy measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : CONFi gure: FLCDMA2K | RLCDMA2K: MACCuracy

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : CONFi gure: FLCDMA2K: MACCuracy  
sets up the analyzer to the default settings for the modulation accuracy measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument [: SELect]

## :CONFigure:*Standard*:OBWidth

Sets up the analyzer to the default settings for the occupied bandwidth measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : CONFi gure: FLCDMA2K | RLCDMA2K: OBWi dth

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : CONFi gure: FLCDMA2K: OBWi dth  
sets up the analyzer to the default settings for the occupied bandwidth measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument [: SELect]

## :CONFigure:*Standard*:PCCHannel

Sets up the analyzer to the default settings for the pilot to code channel measurement under the cdma2000 forward link or reverse link standard.

**Syntax** :CONFi gure:FLCDMA2K|RLCDMA2K: PCCHannel

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :CONFi gure:FLCDMA2K: PCCHannel

sets up the analyzer to the default settings for the pilot to code channel measurement under the cdma2000 forward link standard.

**Related Commands** :INSTrument[:SElect]

## :CONFigure:RLCDMA2K:PVTi me

Sets up the analyzer to the default settings for the gated output power measurement under the cdma2000 reverse link standard.

**Syntax** :CONFi gure:RLCDMA2K: PVTi me

**Arguments** None

**Measurement Modes** DEMRLCDMA2K

**Examples** :CONFi gure:RLCDMA2K: PVTi me

sets up the analyzer to the default settings for the gated output power measurement under the cdma2000 reverse link standard.

**Related Commands** :INSTrument[:SElect]

## :CONFigure:*Standard*:SEMask

Sets up the analyzer to the default settings for the spectrum emission mask measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : CONFi gure: FLCDMA2K | RLCDMA2K: SEMask

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : CONFi gure: FLCDMA2K: SEMask  
sets up the analyzer to the default settings for the spectrum emission mask measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[: SELect]

# :DISPlay Commands

---

**NOTE.** Throughout the header descriptions in this section, the word **Standard** in *italics* is substituted for either of the following two measurement standards; **FLCDMA2K** (*cdma2000 forward link*) or **RLCDMA2K** (*cdma2000 reverse link*).

---

The :DISPlay commands control how measurement data is shown on the screen. These commands are divided into the following subgroups:

Table 3-8: :DISPlay command subgroups

Command header	Function	Page number
:DISPlay: <i>Standard</i> :CCDF	Controls display of the CCDF measurement.	Page 3-18
:DISPlay: <i>Standard</i> :DDEMod	Controls display of the digital modulation related measurements.	Page 3-24
:DISPlay: <i>Standard</i> :SPECTrum	Controls the spectrum display.	Page 3-34
:DISPlay:FLCDMA2K:WAVeform	Controls the time domain display.	Page 3-38

## :DISPlay:*Standard*:CCDF Subgroup

The :DISPlay:*Standard*:CCDF commands control the CCDF view in the CCDF measurement under the cdma2000 forward link or reverse link standard.

**Command Tree**

```
:DISPlay
  :FLCDMA2K|RLCDMA2K
  :CCDF
    :LINE
      :GAUSSian
        [:STATe]      <boolean>
      :REFERENCE
        [:STATe]      <boolean>
      :STORE
    :X
      [:SCALE]
        :AUTO          <boolean>
        :MAXIMUM       <numeric_value>
        :OFFSET        <numeric_value>
    :Y
      [:SCALE]
        :FIT
        :FULL
        :MAXIMUM
        :MINIMUM
```

### :DISPlay:*Standard*:CCDF:LINE:GAUSSian[:STATe]

Determines whether to display the Gaussian line on the CCDF view.

**Syntax**

```
:DISPlay:FLCDMA2K|RLCDMA2K:CCDF:LINE:GAUSSian[:STATe] <boolean>
:DISPlay:FLCDMA2K|RLCDMA2K:CCDF:LINE:GAUSSian[:STATe]?
```

**Arguments**

```
<boolean> ::= {ON|OFF|1|0}
{ON|1}   enables the Gaussian line display.
{OFF|0}  disables the Gaussian line display.
```

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples**

```
:DISPlay:FLCDMA2K:CCDF:LINE:GAUSSian ON
displays the Gaussian line on the CCDF view under the cdma2000 forward link standard.
```

**:DISPlay:*Standard*:CCDF:LINE:REFerence[:STATe]**

Determines whether to display the most recently stored reference line on the CCDF view. This command is only available when a reference line is stored in the instrument memory.

**Syntax** :DISPlay:*Standard*:CCDF:LINE:REFerence[:STATe] <bool ean>

:DISPlay:*Standard*:CCDF:LINE:REFerence[:STATe]?

**Arguments** <bool ean> ::= {ON|OFF|1|0}

{ON|1} enables to display the reference line.

{OFF|0} disables to display the reference line.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples**

:DISPlay:*Standard*:CCDF:LINE:REFerence ON

displays the most recently stored reference line on the CCDF view under the cdma2000 forward link standard.

**Related Commands** :DISPPlay:*Standard*:CCDF:LINE:REFerence:STORe

**:DISPlay:*Standard*:CCDF:LINE:REFerence:STORe**

Stores the line currently being displayed on the CCDF view as a reference line.

**Syntax** :DISPlay:*Standard*:CCDF:LINE:REFerence:STORe

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples**

:DISPlay:*Standard*:CCDF:LINE:REFerence:STORe

stores the line currently being displayed on the CCDF view as a reference line under the cdma2000 forward link standard.

**Related Commands** :DISPPlay:*Standard*:CCDF:LINE:REFerence[:STATe]

## :DISPlay:*Standard*:CCDF:X[:SCALe]:AUTO (?)

Determines whether to automatically set the horizontal, or power, scale in the CCDF view.

**Syntax** : DI SPI ay: FLCDMA2K | RLCDMA2K: CCDF: X[: SCALe]: AUTO <bool ean>

: DI SPI ay: FLCDMA2K | RLCDMA2K: CCDF: X[: SCALe]: AUTO?

**Arguments** <bool ean>: : ={ON|OFF|1|0}  
{ON|1} specifies that the horizontal scale is set automatically.  
{OFF|0} specifies that the horizontal scale is set manually (default).  
Use the :DISPlay:*Standard*:CCDF:X[:SCALe]:MAXimum and DISPlay:*Standard*:CCDF:X[:SCALe]:OFFSet commands to set the horizontal axis.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DI SPI ay: FLCDMA2K: CCDF: X: SCALe: AUTO ON  
specifies that the horizontal scale is set automatically on the CCDF view under the cdma2000 forward link standard.

**Related Commands** :DI SPI ay: FLCDMA2K | RLCDMA2K: CCDF: X[: SCALe]: MAXimum  
:DI SPI ay: FLCDMA2K | RLCDMA2K: CCDF: X[: SCALe]: OFFSet

## :DISPlay:*Standard*:CCDF:X[:SCALe]:MAXimum (?)

Sets or queries the maximum horizontal, or power, scale in the CCDF view.

**Syntax** : DI SPI ay: FLCDMA2K | RLCDMA2K: CCDF: X[: SCALe]: MAXimum <numer i c\_val ue>

: DI SPI ay: FLCDMA2K | RLCDMA2K: CCDF: X[: SCALe]: MAXimum?

**Arguments** <numer i c\_val ue>: :=<NRF> specifies the maximum horizontal value.  
Range: 0 to 15.01 dB

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DI SPI ay: FLCDMA2K: CCDF: X: SCALe: MAXimum 15dB  
sets the maximum horizontal value to 15 dB on the CCDF view under the cdma2000 forward link standard.

**Related Commands** :DI SPI ay: FLCDMA2K | RLCDMA2K: CCDF: X[: SCALe]: AUTO

**:DISPlay:*Standard*:CCDF:X[:SCALe]:OFFSet (?)**

Sets or queries the start value of the horizontal axis in the CCDF view.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:CCDF:X[:SCALe]:OFFSet <numer ic\_val ue>  
 :DISPlay:FLCDMA2K|RLCDMA2K:CCDF:X[:SCALe]:OFFSet?

**Arguments** <numer ic\_val ue> ::= <NRf> specifies the start value of the horizontal axis.  
 Range: 0 to 15.01 dB

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:CCDF:X:SCALe:OFFSet 10dB  
 sets the start value of the horizontal axis to 10 dB on the CCDF view under the cdma2000 forward link standard.

**Related Commands** :DISPlay:FLCDMA2K|RLCDMA2K:CCDF:X[:SCALe]:AUTO

**:DISPlay:*Standard*:CCDF:Y[:SCALe]:FIT**

Runs auto-scale on the CCDF view. The auto-scale automatically sets the start value and scale of the vertical axis so that the whole waveform is displayed on the screen.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:CCDF:Y[:SCALe]:FIT

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:CCDF:Y:SCALe:FIT  
 runs auto scale on the CCDF view under the cdma2000 forward link standard.

## :DISPlay:*Standard*:CCDF:Y[:SCALe]:FULL

Sets the vertical axis to the default full-scale value in the CCDF view.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:CCDF:Y[:SCALe]:FULL

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:CCDF:Y:SCALe:FULL  
sets the vertical axis to the default full-scale value in the CCDF view under the cdma2000 forward link standard.

## :DISPlay:*Standard*:CCDF:Y[:SCALe]:MAXimum (?)

Sets or queries the maximum vertical value (top end) in the CCDF view.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:CCDF:Y[:SCALe]:MAXimum <numerical\_value>

:DISPlay:FLCDMA2K|RLCDMA2K:CCDF:Y[:SCALe]:MAXimum?

**Arguments** <numerical\_value> ::= <NRF> specifies the maximum vertical value.  
Range: 10 E-9 to 100%

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:CCDF:Y:SCALe:MAXimum 90PCT  
sets the maximum vertical value to 90% in the CCDF view under the cdma2000 forward link standard.

**:DISPlay:*Standard*:CCDF:Y[:SCALe]:MINimum (?)**

Sets or queries the minimum vertical value (bottom end) in the CCDF view.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:CCDF:Y[:SCALe]:MINimum <numeric\_value>  
:DISPlay:FLCDMA2K|RLCDMA2K:CCDF:Y[:SCALe]:MINimum?

**Arguments** <numeric\_value> ::= <NRf> specifies the minimum vertical value.  
Range: 10 E-9 to 100%

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:CCDF:Y:SCALe:MINimum 20PCT  
sets the minimum vertical value to 20% in the CCDF view under the cdma2000 forward link standard.

## :DISPlay:*Standard*:DDEMod Subgroup

The :DISPlay:*Standard*:DDEMod commands control display of the main view and subview for the digital modulation related measurement under the cdma2000 forward link or reverse link standard.

<b>Command Tree</b>	<b>:DISPlay</b>	<b>:Standard</b>	<b>:DDEMod</b>	
				:FLCDMA2K RLCDMA2K
				:DDEMod
				:MView
				:CORDER HADamard BREVerse
				:FORMAT CDPower MAccuracy EVM MERRor
				PERRor PCGRam STABLe IQPower
				:X
				[:SCALE] <numerical_value>
				:OFFSET <numerical_value>
				:RANGE <numerical_value>
				:Y
				[:SCALE]
				:FIT
				:FULL
				:OFFSET <numerical_value>
				:PUNI t RELative ABSolute
				:RANGE <numerical_value>
				:SView
				:FORMAT SPECtrum IQPower CONST EVM
				MERRor PERRor
				:X
				[:SCALE] <numerical_value>
				:OFFSET <numerical_value>
				:RANGE <numerical_value>
				:Y
				[:SCALE]
				:FIT
				:FULL
				:OFFSET <numerical_value>
				:RANGE <numerical_value>

## :DISPlay:*Standard*:DDEMod:MView:CORDer (?)

Sets or queries the code order of the main view in the digital modulation related measurement. This command is only available when the code domain power measurement is enabled and the :DISPlay:*Standard*:MView:FORMAT command is set to CDPower or PCGram.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MView:CORDer {HADamard|BREVerse}

:DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MView:CORDer?

**Arguments** HADamard specifies the hadamard code order.  
BREVerse specifies bit reverse.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:DDEMod:MView:CORDer HADamard  
selects the hadamard code order for the code domain power measurement under the cdma2000 forward link standard.

**Related Commands** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MView:FORMAT

## :DISPlay:*Standard*:DDEMod:VIEW:FORMAT (?)

Selects or queries the display format of the main view in the digital modulation related measurement.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:VIEW:FORMAT {CDPower|MACCuracy|EVM|MERRor|PERRor|PCGRam|STABle|IQPower}  
:DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:VIEW:FORMAT?

**Arguments** The arguments and display formats are listed below:

Argument	Display format
CDPower	Code domain power
MACCuracy	Modulation accuracy
EVM	Error vector magnitude (EVM)
MERRor	Amplitude error
PERRor	Phase error
PCGRam	Power codogram
STABle	Symbol table
IQPower	IQ power graph

---

**NOTE.** The arguments CDPower, PCGram, and IQPower are available only when the [:SENSe]:Standard:MEASurement command is set to CDPower. The arguments MACCuracy, EVM, MERRor, PERRor, and STABle are available only when the [:SENSe]:Standard:MEASurement command is set to MACCuracy.

---

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:DDEMod:VIEW:FORMAT CDPower  
selects the code domain power measurement under the cdma2000 forward link standard.

**Related Commands** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:SVIEW:FORMAT  
[:SENSe]:FLCDMA2K|RLCDMA2K:MEASurement

**:DISPlay:*Standard*:DDEMod:MVlew:X[:SCALe]:OFFSet (?)**

Sets or queries the minimum horizontal value (left end) in the main view during the digital modulation related measurement.

**Syntax** :DISPIay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:X[:SCALe]:OFFset  
<numerical\_value>

:DISPIay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:X[:SCALe]:OFFset?

**Arguments** <numerical\_value>: :=<NRF> specifies the minimum horizontal value in the main view. The valid range depends on the display format. Refer to Table C-1 in *Appendix C*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPIay:FLCDMA2K:DDEMod:MVlew:X:SCALe:OFFSet 10  
sets the minimum horizontal value to 10 chips when the main view displays EVM under the cdma2000 forward link standard.

**Related Commands** :DISPIay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:FORMAT

**:DISPlay:*Standard*:DDEMod:MVlew:X[:SCALe]:RANGE (?)**

Sets or queries the full-scale value of the horizontal axis in the main view during the digital modulation related measurement.

**Syntax** :DISPIay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:X[:SCALe]:RANGE  
<numerical\_value>

:DISPIay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:X[:SCALe]:RANGE?

**Arguments** <numerical\_value>: :=<NRF> specifies the full-scale value of the horizontal axis in the main view. The valid range depends on the display format. Refer to Table C-1 in *Appendix C*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPIay:FLCDMA2K:DDEMod:MVlew:X:SCALe:RANGE 512  
sets the full-scale value of the horizontal axis to 512 chips when the main view displays EVM under the cdma2000 forward link standard.

**Related Commands** :DISPIay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:FORMAT

## :DISPlay:*Standard*:DDEMod:MView:Y[:SCALe]:FIT

Runs auto-scale on the main view during the digital modulation related measurement. The auto-scale automatically sets the start value and scale of the vertical axis so that the whole waveform is displayed on the screen.

**Syntax** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: MView: Y[: SCALe]: FIT

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DISPI ay: FLCDMA2K: DDEMod: MView: Y: SCALe: FIT  
runs auto scale on the main view under the cdma2000 forward link standard.

**Related Commands** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: MView: FORMat

## :DISPlay:*Standard*:DDEMod:MVew:Y[:SCALe]:FULL

Sets the vertical axis in the main view to the default full-scale value during the digital modulation related measurement.

**Syntax** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: MVew: Y[: SCALe]: FULL

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DISPI ay: FLCDMA2K: DDEMod: MVew: Y: SCALe: FULL  
sets the main view's vertical axis to the default full-scale value under the cdma2000 forward link standard.

**Related Commands** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: MVew: FORMat

**:DISPlay:*Standard*:DDEMod:MVlew:Y[:SCALe]:OFFSet (?)**

Sets or queries the minimum vertical value in the main view (bottom end) during the digital modulation related measurement.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:Y[:SCALe]:OFFSet  
<numerical\_value>

:DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:Y[:SCALe]:OFFSet?

**Arguments** <numerical\_value> ::= <NRF> specifies the minimum vertical value in the main view. The valid range depends on the display format. Refer to Table C-1 in *Appendix C*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:DDEMod:MVlew:Y:SCALe:OFFSet -1mPCT  
sets the minimum vertical value to -1m% when the main view displays EVM under the cdma2000 forward link standard.

**Related Commands** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:FORMAT

**:DISPlay:*Standard*:DDEMod:MVlew:Y[:SCALe]:PUNit (?)**

Selects or queries the unit on the Y, or power, axis in the main view during the digital modulation related measurement. This command is only available when the :DISPlay:*Standard*:DDEMod:MVlew:FORMAT command is set to CDPower or PCGRam.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:Y[:SCALe]:PUNi t  
{RELative|ABSolute}

:DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:Y[:SCALe]:PUNi t?

**Arguments** RELative represents the relative channel power to the total power of all the channels along the Y axis in dB.  
ABSolute represents the absolute power of each channel along the Y axis in dBm.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:DDEMod:MVlew:Y:SCALe:PUNi t ABSolute  
sets the Y axis unit in the main view to Absolute under the cdma2000 forward link standard.

**Related Commands** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:FORMAT

**:DISPlay:*Standard*:DDEMod:MVlew:Y[:SCALe]:RANGe (?)**

Sets or queries the full-scale value of the vertical axis in the main view during the digital modulation related measurement.

**Syntax** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: MVlew: Y[: SCALe]: RANGe  
<numer ic\_val ue>

: DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: MVlew: Y[: SCALe]: RANGe?

**Arguments** <numer ic\_val ue> ::= <NRf> specifies the full-scale value of the vertical axis in the main view. The valid range depends on the display format. Refer to Table C-1 in *Appendix C*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DISPI ay: FLCDMA2K: DDEMod: MVlew: Y: SCALe: RANGe 10PCT  
sets the full-scale value of the vertical axis to 10% when the main view displays EVM under the cdma2000 forward link standard.

**Related Commands** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: MVlew: FORMat

**:DISPlay:*Standard*:DDEMod:SVlew:FORMAT (?)**

Selects or queries the display format of the subview in the digital modulation related measurement.

**Syntax** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: SVlew: FORMat {SPECtrum|IQPower |CONStellation|EVM|MERRor|PERRor}

: DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: SVlew: FORMat?

**Arguments** The arguments and display formats are listed below:

Argument	Display format
SPECtrum	Spectrum
IQPower	IQ power graph
CONStellation	Constellation
EVM	Error vector magnitude (EVM)
MERRor	Amplitude error
PERRor	Phase error

---

**NOTE.** The argument *IOPower* is only available when the [:SENSe]:Standard :MEASurement command is set to CDPower or MACCuracy.

---

<b>Measurement Modes</b>	DEMFLCDMA2K, DEMRLCDMA2K
<b>Examples</b>	:DISPlay:FLCDMA2K:DDEMod:SVIew:FORMAT:SPECTrum displays the spectrum in the subview under the cdma2000 forward link standard.
<b>Related Commands</b>	:DISPlay:FLCDMA2K RLCDMA2K:DDEMod:SVIew:FORMAT

## :DISPlay:*Standard*:DDEMod:SVIew:X[:SCALE]:OFFSet (?)

Sets or queries the minimum horizontal value (left end) in the main view during the digital modulation related measurement.

<b>Syntax</b>	:DISPlay:FLCDMA2K RLCDMA2K:DDEMod:SVIew:X[:SCALE]:OFFset <numerical_value>  :DISPlay:FLCDMA2K RLCDMA2K:DDEMod:SVIew:X[:SCALE]:OFFset?
<b>Arguments</b>	<numerical_value>: =<NRf> specifies the minimum horizontal value in the subview. The valid range depends on the display format. Refer to Table C-1 in <i>Appendix C</i> .
<b>Measurement Modes</b>	DEMFLCDMA2K, DEMRLCDMA2K
<b>Examples</b>	:DISPlay:FLCDMA2K:DDEMod:SVIew:X:SCALE:OFFSet 10 sets the minimum horizontal value to 10 chips when the subview displays EVM under the cdma2000 forward link standard.
<b>Related Commands</b>	:DISPlay:FLCDMA2K RLCDMA2K:DDEMod:SVIew:FORMAT

## :DISPlay:*Standard*:DDEMod:SVlew:X[:SCALe]:RANGE (?)

Sets or queries the full-scale value of the horizontal axis in the subview during the digital modulation related measurement.

**Syntax** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: SVI ew: X[: SCALe]: RANGE  
<numer ic\_val ue>

: DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: SVI ew: X[: SCALe]: RANGE?

**Arguments** <numer ic\_val ue> ::= <NRF> specifies the full-scale value of the horizontal axis in the subview. The valid range depends on the display format. Refer to Table C-1 in *Appendix C*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DISPI ay: FLCDMA2K: DDEMod: MVI ew: X: SCALe: RANGE 512  
sets the full-scale value of the horizontal axis to 512 chips when the subview displays EVM under the cdma2000 forward link standard.

**Related Commands** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: SVI ew: FORMat

## :DISPlay:*Standard*:DDEMod:SVlew:Y[:SCALe]:FIT

Runs auto-scale on the subview during the digital modulation related measurement. The auto-scale automatically sets the start value and scale of the vertical axis so that the whole waveform is displayed on the screen.

**Syntax** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: SVI ew: Y[: SCALe]: FIT

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DISPI ay: FLCDMA2K: DDEMod: SVI ew: Y: SCALe: FIT  
runs auto scale on the subview under the cdma2000 forward link standard.

**Related Commands** : DISPI ay: FLCDMA2K | RLCDMA2K: DDEMod: SVI ew: FORMat

**:DISPlay:*Standard*:DDEMod:SVlew:Y[:SCALe]:FULL**

Sets the vertical axis in the subview to the default full-scale value during the digital modulation related measurement.

**Syntax** :DISPlay:*Standard*:DDEMod:SVlew:Y[:SCALe]:FULL

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:*Standard*:DDEMod:SVlew:Y:SCALe:FULL  
sets the subview's vertical axis to the default full-scale value under the cdma2000 forward link standard.

**Related Commands** :DISPlay:*Standard*:DDEMod:SVlew:FORMAT

**:DISPlay:*Standard*:DDEMod:SVlew:Y[:SCALe]:OFFSet (?)**

Sets or queries the minimum vertical value in the subview (bottom end) during the digital modulation related measurement.

**Syntax** :DISPlay:*Standard*:DDEMod:SVlew:Y[:SCALe]:OFFSet  
<numeric\_value>

:DISPlay:*Standard*:DDEMod:SVlew:Y[:SCALe]:OFFSet?

**Arguments** <numeric\_value>: :=<NRF> specifies the minimum vertical value in the subview. The valid range depends on the display format. Refer to Table C-1 in *Appendix C*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:*Standard*:DDEMod:SVlew:Y:SCALe:OFFSet -100dBm  
sets the minimum vertical value to -100 dBm when the subview displays spectrum under the cdma2000 forward link standard.

**Related Commands** :DISPlay:*Standard*:DDEMod:SVlew:FORMAT

## :DISPlay:*Standard*:DDEMod:SVlew:Y[:SCALe]:RANGe (?)

Sets or queries the full-scale value of the vertical axis in the subview during the digital modulation related measurement.

**Syntax** : DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:SVIew:Y[:SCALe]:RANGE  
<numeric\_value>

: DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:SVIew:Y[:SCALe]:RANGE?

**Arguments** <numeric\_value> ::= <NRF> specifies the full-scale value of the vertical axis in the subview. The valid range depends on the display format. Refer to Table C-1 in *Appendix C*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DISPlay:FLCDMA2K:DDEMod:SVIew:Y:SCALe:RANGE 100dB  
sets the full-scale value of the vertical axis to 100 dB when the subview displays spectrum under the cdma2000 forward link standard.

**Related Commands** : DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:SVIew:FORMAT

## :DISPlay:*Standard*:SPECtrum Subgroup

The :DISPlay:*Standard*:SPECtrum commands control the spectrum display in the channel power, intermodulation, spectrum emission mask (SEM), and occupied bandwidth measurements under the cdma2000 forward link or reverse link standard.

**Command Tree**

```
:DISPlay
  :FLCDMA2K|RLCDMA2K
  :SPECtrum
  :X
    [:SCALE]
    :OFFSet      <numeric_value>
    :PDIVison   <numeric_value>
  :Y
    [:SCALE]
    :FIT
    :FULL
    :OFFSet      <numeric_value>
    :PDIVison   <numeric_value>
```

**:DISPlay:*Standard*:SPECTrum:X[:SCALe]:OFFSet (?)**

Sets or queries the minimum value (left edge) of the horizontal axis (frequency) in the spectrum view.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:SPECTrum:X[:SCALe]:OFFSet  
<numerical\_value>

:DISPlay:FLCDMA2K|RLCDMA2K:SPECTrum:X[:SCALe]:OFFSet?

**Arguments** <numerical\_value>: :=<NRf> specifies the minimum horizontal value in the spectrum view. The valid range depends on the measurement frequency band in the [:SENSe]:FREQuency:BAND command. Refer to the *WCA230A & WCA280A Portable Wireless Communication Analyzers Programmer Manual*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:SPECTrum:X:SCALe:OFFSet 100MHz  
sets the minimum horizontal value to 100 MHz in the spectrum view under the cdma2000 forward link standard.

**:DISPlay:*Standard*:SPECTrum:X[:SCALe]:PDIVisiOn (?)**

Sets or queries the horizontal, or frequency, scale (per division) in the spectrum view.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:SPECTrum:X[:SCALe]:PDIVisiOn  
<numerical\_value>

:DISPlay:FLCDMA2K|RLCDMA2K:SPECTrum:X[:SCALe]:PDIVisiOn?

**Arguments** <numerical\_value>: :=<NRf> specifies the horizontal scale in the spectrum view. The valid range depends on the measurement frequency band in the [:SENSe]:FREQuency:BAND command. Refer to the *WCA230A & WCA280A Portable Wireless Communication Analyzers Programmer Manual*.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:SPECTrum:X:SCALe:PDIVisiOn 100kHz  
sets the horizontal scale to 100 kHz/div in the spectrum view under the cdma2000 forward link standard.

## :DISPlay:*Standard*:SPECtrum:Y[:SCALe]:FIT

Runs auto-scale on the spectrum view. The auto-scale automatically sets the start value and scale of the vertical axis so that the whole waveform is displayed on the screen.

**Syntax** : DI SPI ay: FLCDMA2K|RLCDMA2K: SPECtrum: Y[: SCALe]: FIT

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DI SPI ay: FLCDMA2K: SPECtrum: Y: SCALe: FIT  
runs auto-scale on the spectrum view under the cdma2000 forward link standard.

## :DISPlay:*Standard*:SPECtrum:Y[:SCALe]:FULL

Sets the vertical axis to the default full-scale value in the spectrum view.

**Syntax** : DI SPI ay: FLCDMA2K|RLCDMA2K: SPECtrum: Y[: SCALe]: FULL

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : DI SPI ay: FLCDMA2K: SPECtrum: Y: SCALe: FULL  
sets the vertical axis to the default full-scale value in the spectrum view under the cdma2000 forward link standard.

## :DISPlay:*Standard*:SPECtrum:Y[:SCALe]:OFFSet (?)

Sets or queries the minimum vertical, or amplitude value (bottom end) in the spectrum view.

**Syntax** : DI SPI ay: FLCDMA2K|RLCDMA2K: SPECtrum: Y[: SCALe]: OFFSet  
<numerical\_value>

: DI SPI ay: FLCDMA2K|RLCDMA2K: SPECtrum: Y[: SCALe]: OFFSet?

**Arguments** <numerical\_value>: : = <NRF> specifies the minimum vertical value.  
Range: -200 to 100 dBm

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:SPECTrum:Y:SCALE:OFFSet -100dBm  
 sets the minimum vertical value to -100 dBm in the spectrum view under the cdma2000 forward link standard.

## :DISPlay:*Standard*:SPECTrum:Y[:SCALE]:PDIVisiOn (?)

Sets or queries the vertical, or amplitude, scale (per division) in the spectrum view.

**Syntax** :DISPlay:FLCDMA2K|RLCDMA2K:SPECTrum:Y[:SCALE]:PDIVisiOn  
 <numeric\_value>

:DISPlay:FLCDMA2K|RLCDMA2K:SPECTrum:Y[:SCALE]:PDIVisiOn?

**Arguments** <numeric\_value> ::= <NRF> specifies the vertical scale in the spectrum view.  
 Range: 0 to 10 dB/div

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :DISPlay:FLCDMA2K:SPECTrum:Y:SCALE:PDIVisiOn 10  
 sets the vertical scale to 10 dB/div in the spectrum view under the cdma2000 forward link standard.

## :DISPlay:RLCDMA2K:WAveform Subgroup

The :DISPlay:RLCDMA2K:WAveform commands control the time domain display in the main view of the gated output power measurement under the cdma2000 reverse link standard.

**Command Tree**

```
:DISPlay
  :RLCDMA2K
    :WAveform
      :X
        [:SCALE]
          :OFFSet      <numeric_value>
          :PDIVison   <numeric_value>
      :Y
        [:SCALE]
          :FIT
          :FULL
          :OFFSet      <numeric_value>
          :PDIVison   <numeric_value>
```

### :DISPlay:RLCDMA2K:WAveform:X[:SCALE]:OFFSet (?)

Sets or queries the minimum value (left edge) of the horizontal axis (frequency) in the time domain display.

**Syntax**    :DISPlay:RLCDMA2K:WAveform:X[:SCALE]:OFFSet <numeric\_value>

              :DISPlay:RLCDMA2K:WAveform:X[:SCALE]:OFFSet?

**Arguments**    <numeric\_value> ::=<NRF> specifies the minimum horizontal value.  
Range: approximately -416.67 µs to approximately 415 µs (since the resolution of the time axis depends on the span setting of the instrument, the upper and lower limit values are set to the nearest value of a multiple of its resolution).

**Measurement Modes**    DEMRLCDMA2K

**Examples**    :DISPlay:RLCDMA2K:WAveform:X:SCALE:OFFSet -100us  
sets the minimum horizontal value to -100 µs in the time domain display under the cdma2000 reverse link standard.

**:DISPlay:RLCDMA2K:WAveform:X[:SCALe]:PDIVisiOn (?)**

Sets or queries the horizontal, or time, scale (per division) in the time domain display.

**Syntax** :DISPlay:RLCDMA2K:WAveform:X[:SCALe]:PDIVisiOn <numeric\_value>

:DISPlay:RLCDMA2K:WAveform:X[:SCALe]:PDIVisiOn?

**Arguments**

<numeric\_value> ::= <NRf> specifies the horizontal scale.

Range: approximately 0.1627 μs to approximately 833.33 μs (since the resolution of the time axis depends on the span setting of the instrument, the upper and lower limit values are set to the nearest value of a multiple of its resolution).

**Measurement Modes**

DEMRLCDMA2K

**Examples**

:DISPlay:FLCDMA2K:WAveform:X:SCALe:PDIVisiOn 10us

sets the horizontal scale to 10 μs/div in the time domain display under the cdma2000 forward link standard.

**:DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:FIT**

Runs auto-scale on the time domain display. The auto-scale automatically sets the start value and scale of the vertical axis so that the whole waveform is displayed on the screen.

**Syntax**

:DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:FIT

**Arguments**

None

**Measurement Modes**

DEMRLCDMA2K

**Examples**

:DISPlay:FLCDMA2K:WAveform:Y:SCALe:FIT

runs auto-scale on the time domain display under the cdma2000 reverse link standard.

## :DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:FULL

Sets the vertical axis to the default full-scale value in the time domain display.

**Syntax** : DI SPI ay: RLCDMA2K: WAveform: Y[: SCALe] : FULL

**Arguments** None

**Measurement Modes** DEMRLCDMA2K

**Examples** : DI SPI ay: RLCDMA2K: WAveform: Y: SCALe: FULL

sets the vertical axis to the default full-scale value in the time domain display under the cdma2000 reverse link standard.

## :DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:OFFSet (?)

Sets or queries the minimum vertical, or amplitude value (bottom end) in the time domain display.

**Syntax** : DI SPI ay: RLCDMA2K: WAveform: Y[: SCALe] : OFFSet <numeric\_value>

: DI SPI ay: RLCDMA2K: WAveform: Y[: SCALe] : OFFSet?

**Arguments** <numeric\_value>: : =<NRF> specifies the minimum vertical value.  
Range: -200 to 100 dBm

**Measurement Modes** DEMRLCDMA2K

**Examples** : DI SPI ay: RLCDMA2K: WAveform: Y: SCALe: OFFSet -100dBm

sets the minimum vertical value to -100 dBm in the time domain display under the cdma2000 reverse link standard.

## :DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:PDIVisi on (?)

Sets or queries the vertical, or amplitude, scale (per division) in the time domain display.

**Syntax** :DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:PDIVisi on <numer i c\_val ue>

:DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:PDIVisi on?

**Arguments** <numer i c\_val ue> ::=<NRf> specifies the vertical scale in the time domain display.  
Range: 1.0 E-5 to 10 dB

**Measurement Modes** DEMRLCDMA2K

**Examples** :DISPlay:RLCDMA2K:WAveform:Y:SCALe:PDIVisi on 10dB  
sets the vertical scale to 10 dB/div in the time domain display under the cdma2000 reverse link standard.



# :FETCh Commands

The :FETCh commands retrieve the measurements from the data taken by the latest :INITiate command.

If you want to perform a FETCh operation on fresh data, use the :READ commands on page 3-63. The :READ commands acquire a new input signal and fetch the measurement results from the data.

---

**NOTE.** Throughout the header descriptions in this section, the word **Standard** in *italics* is substituted for either of the following two measurement standards; **FLCDMA2K** (*cdma2000 forward link*) or **RLCDMA2K** (*cdma2000 reverse link*).

---

## Command Tree

```
:FETCh
  :FLCDMA2K|RLCDMA2K
    :ACPower?
    :CCDF?
    :CDPower?      RESUlt|CDPower|IQPower
    :CHPower?
    :IM?
    :MACAccuracy?   RESUlt|MACAccuracy|EVM|MERRor|PERRor|STABlE
    :OBWidth?
    :PCCHannel?
    :PVTime?
    :SEMask?
    :Distribution
      :CCDF?
    :TAMPItude
      :PVTime?
    :SPECTrum
      :ACPower?
      :CHPower?
      :IM?
      :OBWidth?
```

## :FETCh:*Standard*:ACPower?

Returns the results of the ACPR measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K|RLCDMA2K: ACPower?

**Arguments** None

**Returns** <Pass\_fail>, <Chpower>, <Acpr1>, <Acpr2>, <Acpr3>, <Acpr4>, <Acpr5>, <Acpr6>, <Acpr7>, <Acpr8>, <Acpr9>, <Acpr10>, <Acpr11>, <Acpr12>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

<Chpower> ::= <NRF> is the channel power measured value in dBm.

<Acpr1> ::= <NRF> is the first adjacent channel ACPR in dBc.

<Acpr2> ::= <NRF> is the second adjacent channel ACPR in dBc.

<Acpr3> ::= <NRF> is the third adjacent channel ACPR in dBc.

.

.

<Acpr10> ::= <NRF> is the tenth adjacent channel ACPR in dBc.

<Acpr11> ::= <NRF> is the eleventh adjacent channel ACPR in dBc.

<Acpr12> ::= <NRF> is the twelfth adjacent channel ACPR in dBc.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: ACPower?

might return 0, -2.045E+001, -6.461E+001, -4.379E+001, -6.576E+001, -6.753E+001, -6.79E+001, -1.0E+038, -1.0E+038, -1.0E+038, -1.0E+038, -1.0E+038, -1.0E+038 for the ACPR measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[:SELect]

## :FETCh:*Standard*:CCDF?

Returns the results of the CCDF measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K | RLCDMA2K: CCDF?

**Arguments** None

**Returns** <Mean\_power>, <Peak\_power>, <Crest\_factor>

Where

<Mean\_power> ::= <NRF> is the average power in dBm.

<Peak\_power> ::= <NRF> is the peak power in dBm.

<Crest\_factor> ::= <NRF> is the crest factor in dB.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: CCDF?

might return -1.757E+001, -9.53E+000, 8.04E+000 for the CCDF measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[: SElect]

## :FETCh:*Standard*:CDPower?

Returns the results of the code domain power measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K|RLCDMA2K: CDPower? {RESul t|CDPower|IQPower}

**Arguments**

RESul t	measurement result
CDPower	relative/absolute power values of each code
IQPower	each I/Q symbol powers of selected code

**Returns**

■ **RESult:**

<Pass\_fail>, <Total\_power>, <ACP\_max>, <ACP\_avg>, <ACP\_total>, <No\_AC>, <ICP>, <EVM\_peak>, <EVM\_rms>, <Mrror\_peak>, <Mrror\_rms>, <Perror\_peak>, <Perror\_rms>

Where

<Pass\_fail>: :={1|0} is the measurement result; 1: Pass or 0: Fail.  
<Total\_power>: :=<NRF> is the channel power total value in dBm.  
<ACP\_max>: :=<NRF> is the active channel power maximum value in dBc.  
<ACP\_avg>: :=<NRF> is the active channel power average value in dBc.  
<ACP\_total>: :=<NRF> is the active channel power total value in dBc.  
<No\_AC>: :=<NR1> is the number of active channels.  
<ICP>: :=<NRF> is the maximum inactive channel power in dBc.  
<EVM\_peak>: :=<NRF> is the EVM peak value in %.  
<EVM\_rms>: :=<NRF> is EVM rms value in %.  
<Mrror\_peak>: :=<NRF> is the magnitude error peak value in %.  
<Mrror\_rms>: :=<NRF> is the magnitude error rms value in %.  
<Perror\_peak>: :=<NRF> is the phase error peak value in degrees.  
<Perror\_rms>: :=<NRF> is the phase error rms value in degrees.

■ **CDPower:**

#<Num\_digits>, <Num\_byte>, <ICpower(1)>, <QCpower(1)>, . . . ,  
<ICpower(n)>, <QCpower(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.   
<Num\_byte> is the number of bytes of the data that follows.  
<ICpower(n)> and <QCpower(n)> is the relative or absolute power value for each code in dB or dBm. When the unit on the Y axis of main view is set to RELative, the relative power value is selected. When the unit on the Y axis of main view is set to ABSolute, the absolute power value is selected. Four-byte little endian floating-point format specified IEEE 488.2. n: Max 128  
FLCDMA2K RC1/RC2: n=Max 64, RC3/RC4/RC5: n=Max 128  
RLCDMA2K RC3/RC4: n=Max 128

■ **IQPower:**

```
#<Num_digit>, <Num_byte>, <I power(1)>, <Qpower(1)>, . . . , <I power(n)>, <Qpower(n)>
```

Where

<Num\_digit> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follows.

<I power(n)> and <Qpower(n)> is the each I/Q symbol power of selected code.

Four-byte little endian floating-point format specified IEEE 488.2.

Measurement level:

Chip: n=Max 1536

Symbol:

FLCDMA2K RC1/RC2: n=Max 24, RC3/RC4/RC5: n=Max 382

RLCDMA2K RC3/RC4: n=Max: 768

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples**

:FETCh: FLCDMA2K: CDPower? RESul t

might return 0, -3. 32076616615568E+001, -2. 33279216292314E-004, -2. 33279216292314E-004, -2. 33279216292314E-004, 16, -5. 53129098248105E+001, 1. 05323582245638E-001, 9. 3576108554992E-002, -9. 71313482041643E-002, 7. 27630326866468E-002, 4. 19705794596374E-002, 3. 37042668803851E-002 for the code domain power measurement for the cdma2000 forward link standard.

**Related Commands** :INSTrument[:SElect]

## :FETCh:*Standard*:CHPower?

Returns the results of the channel power measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K|RLCDMA2K: CHPower?

**Arguments** None

**Returns** <Pass\_fail>, <chpower>, <power\_densit>

Where

<Pass\_fail>:={1|0} is the measurement result; 1: Pass or 0: Fail.

<Chpower>:=<NRF> is the channel power measured value in dBm.

<Power\_densit>:=<NRF> is the power density measured value in dBm/Hz.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: CHPower?

might return 1, -2.0339E+001, -8.1238E+001 for the channel power measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[:SELect]

## :FETCh:*Standard*:IM?

Returns the results of the intermodulation measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K|RLCDMA2K: IM?

**Arguments** None

**Returns** <Pass\_fail>, <L\_channel>, <U\_channel>, <L3\_Lower>, <L3\_Upper>, <U3\_Lower>, <U3\_Upper>, <L5\_Lower>, <L5\_Upper>, <U5\_Lower>, <U5\_Upper>

Where

<Pass\_fail>:={1|0} is the measurement result; 1: Pass or 0: Fail.

<L\_channel>:=<NRF> is the lower channel measured value in dBm.

<U\_channel>:=<NRF> is the upper channel measured value in dBm.

<L3\_Lower>:=<NRF> is the lower third order (lower) measured value in dBc.

<L3\_Upper>:=<NRF> is the lower third order (upper) measured value in dBc.

<U3\_Lower>:=<NRF> is the upper third order (lower) measured value in dBc.

<U3\_Upper>:=<NRF> is the upper third order (upper) measured value in dBc.

<L5\_Lower>::=<NRF> is the lower fifth order (lower) measured value in dBc.  
<L5\_upper>::=<NRF> is the lower fifth order (upper) measured value in dBc.  
<U5\_Lower>::=<NRF> is the upper fifth order (lower) measured value in dBc.  
<U5\_upper>::=<NRF> is the upper fifth order (upper) measured value in dBc.

When each value is not present, the value of -1000 is returned.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :FETCh:FLCDMA2K:IM?  
might return 1, -2.061E+001, -5.501E+001, -1.66E+001, 1.78E+001,  
-4.76E+001, -1.32E+001, -4.73E+001, -1.29E+001, -5.1E+001, -1.66E+001  
for the intermodulation measurement under the cdma2000 forward link standard.

**Related Commands** :INSTrument[:SElect]

## :FETCh:*Standard*:MACCuracy?

Returns the results of the modulation accuracy measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh:FLCDMA2K|RLCDMA2K:MACCuracy? {RESul t|MACCuracy|EVM|MERRor|PERRor|STABI e}

<b>Arguments</b>	RESul t	measurement result
	MACCuracy	I/Q position of each symbol
	EVM	EVM of each symbol
	MERRor	magnitude error of each symbol
	PERRor	phase error of each symbol
	STABI e	each symbol data

**Returns** ■ **RESult:**

<Pass\_fai l>, <Rho>, <Peak\_CDE>, <CDE\_code>, <CDE\_I/Q>,  
<EVM\_peak>, <EVM\_rms>, <Mrror\_peak>, <Mrror\_rms>, <Perror\_peak>,  
<Perror\_rms>, <Ferror>, <Org\_offset>, <Tau>

Where

<Pass\_fai l>: : ={1|0} is the measurement result; 1: Pass or 0: Fail.  
<Rho>: : =<NRF> is the measured value of waveform quality (Rho).  
<Peak\_CDE>: : =<NRF> is the code domain error value in dB.  
<CDE\_code>: : =<NR1> is the code number of CDE.  
<CDE\_I/Q>: : =<NR1> is the I/Q channel of CDE. 0: don't care, 1: I, 2: Q.  
<EVM\_peak>: : =<NRF> is the EVM peak value in %.  
<EVM\_rms>: : =<NRF> is EVM rms value in %.  
<Mrror\_peak>: : =<NRF> is the magnitude error peak value in %.  
<Mrror\_rms>: : =<NRF> is the magnitude error rms value in %.  
<Perror\_peak>: : =<NRF> is the phase error peak value in degrees.  
<Perror\_rms>: : =<NRF> is the phase error rms value in degrees.  
<Ferror>: : =<NRF> is the measured value of frequency error in Hz.  
<Org\_offset>: : =<NRF> is the measured value of origin offset in Hz.  
<Tau>: : =<NRF> is the measured value of Tau in seconds.

Tau is only available in the forward link standard.

■ **MACCuracy:**

#<Num\_digi t>, <Num\_byte>, <I positi on(1)>, <0positi on(1)>, . . . ,  
<I positi on(n)>, <Qpositi on(n)>

Where

<Num\_digi t> is the number of digits in <Num\_byte>.  
<Num\_byte> is the number of bytes of the data that follows.

<Iposition(n)> and <Qposition(n)> is the I/Q position of each symbol.  
Four-byte little endian floating-point format specified IEEE 488.2.

Measurement level:

Chip: n=Max 1536

Symbol:

FLCDMA2K RC1/RC2: n=Max 24, RC3/RC4/RC5: n=Max 384

RLCDMA2K RC3/RC4: n=Max: 768

### ■ EVM:

#<Num\_digits>, <Num\_byte>, <EVM(1)>, . . . , <EVM(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follows.

<EVM(n)> is EVM of each symbol. Four-byte little endian floating-point format specified IEEE 488.2.

Measurement level:

Chip: n=Max 1536

Symbol:

FLCDMA2K RC1/RC2: n=Max 24, RC3/RC4/RC5: n=Max 384

RLCDMA2K RC3/RC4: n=Max: 768

### ■ MERRor:

#<Num\_digits>, <Num\_byte>, <Mrror(1)>, . . . , <Mrror(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follows.

<Mrror(n)> is the magnitude error of each symbol. Four-byte little endian floating-point format specified IEEE 488.2.

Measurement level:

Chip: n=Max 1536

Symbol:

FLCDMA2K RC1/RC2: n=Max 24, RC3/RC4/RC5: n=Max 384

RLCDMA2K RC3/RC4: n=Max: 768

**■ PERRor:**

#<Num\_digits>, <Num\_byte>, <Perror(1)>, . . . , <Perror(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follows.

<Perror(n)> is the phase error of each symbol. Four-byte little endian floating-point format specified IEEE 488.2.

Measurement level:

Chip: n=Max 1536

Symbol:

FLCDMA2K RC1/RC2: n=Max 24, RC3/RC4/RC5: n=Max 384

RLCDMA2K RC3/RC4: n=Max: 768

**■ STABle:**

#<Num\_digits>, <Num\_byte>, <Symbol(1)>, . . . , <Symbol(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follows.

<Symbol(n)> is the each symbol data. Four-byte little endian floating-point format specified IEEE 488.2. For FLCDMA2K, this is only available when Measurement Level is set to Symbol. For RLCDMA2K, this is only available when Measurement Level is set to Symbol and Radio Configuration is set to RC1/RC2. In other cases, the value -1000 returns.

RLCDMA2K(RC1/RC2): n=Max 1536

When Measurement Level is set to Symbol:

FLCDMA2K RC1/RC2: n=Max 24, RC3/RC4/RC5: n=Max 384

RLCDMA2K RC3/RC4: n=Max 768

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: MACcuracy? RESult might return 1, 9. 99999124351958E-001, -5. 27257858114915E+001, 28, 1, 1. 05323582245638E-001, 9. 3576108554992E-002, -9. 71313482041643E-002, 7. 27630326866468E-002, 4. 19705794596374E-002, 3. 37042668803851E-002, -2. 75421142578065E+001, -1. 23769373237522E+002, 0. 0E+000 for the modulation accuracy measurement under the cdma2000 forward link measurement.

**Related Commands** : INStrument[: SELect]

## :FETCh:*Standard*:OBWidth?

Fetches the results of the occupied bandwidth measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K | RLCDMA2K: OBWi dth?

**Arguments** None

**Returns** <Pass\_fail>, <obw>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.  
<obw> ::= <NRF> is the occupied bandwidth in Hz.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: OBWi dth?

might return 1, 1. 27333E+006 for the OBW measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[: SElect]

## :FETCh:Standard:PCCHannel?

Fetches the results of the pilot-to-code channel measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K | RLCDMA2K: PCCHannel ?

**Arguments** None

**Returns** <Pass\_fail>, <No\_AC>{, <SF(n)>, <Code\_num(n)>, <Power(n)>, <Timing(n)>, <Phase(n)>, <I\_code(n)>, <Q\_code(n)>}

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

<No\_AC> ::= <NRF> is the number of active channels.

<SF(n)> ::= <NRF> is the spreading factor.

<Code\_num(n)> ::= <NR1> is the code number.

<Power(n)> ::= <NRF> is code domain power measured value in dBm.

<Timing(n)> ::= <NRF> is the pilot channel versus time measured value in seconds.

<Phase(n)> ::= <NRF> is the pilot channel versus phase measured value in radian.

<I\_code(n)> ::= <NRF> is the code domain error of I phase in dBm.

<Q\_code(n)> ::= <NRF> is the code domain error of Q phase in dBm.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: PCCHannel ?

might return 1, 2, 6, 2, -3. 62181797592003E+001, 7. 95659919582192E-009, 2. 46966153831218E-003, -7. 2188511413898E+001, -7. 25107168870122E+001, 6, 34, -3. 62224724925938E+001, -7. 4505805947922E-010, -3. 11469251014973E-003, -7. 1436502569957E+001, -6. 58634460703051E+0010, for the pilot to code channel measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[:SELect]

## :FETCh:RLCDMA2K:PVTime?

Fetches the results of the gated output power measurement under the cdma2000 reverse link standard.

**Syntax** : FETCh: RLCDMA2K: PVTime?

**Arguments** None

**Returns** <Pass\_fail>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

**Measurement Modes** DEMRLCDMA2K

**Examples** : FETCh: RLCDMA2K: PVTime?

might return 1, indicating that the gated output power measurement has passed.

**Related Commands** : INSTRument[: SElect]

## :FETCh:Standard:SEMask?

Fetches the results of the spectrum emission mask measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K | RLCDMA2K: SEMask?

**Arguments** None

**Returns** <Pass\_fail>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: SEMask?

might return 1, indicating that the spectrum emission mask measurement has passed.

**Related Commands** : INSTRument[: SElect]

## :FETCh:*Standard*:DISTribution:CCDF?

Fetches the distribution data of the CCDF measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K | RLCDMA2K: DISTribution: CCDF?

**Arguments** None

**Returns** #<Num\_digits><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the absolute power for each symbol in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.

n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: DISTribution: CCDF?

might return #510240xxx... (1024-byte data) as the results of the CCCDF measurement under the cdma2000 forward link standard.

**Related Commands** : INStrument[: SElect]

## :FETCh:RLCDMA2K:TAMPlitude:PVTi me?

Fetches the time domain amplitude data of the gated output power measurement under the cdma2000 reverse link standard.

**Syntax** : FETCh: RLCDMA2K: TAMPI tude: PVTi me?

**Arguments** None

**Returns** #<Num\_digits><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the absolute power for each symbol in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.  
 n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMRLCDMA2K

**Examples** : FETCh: RLCDMA2K: TAMPI tude: PVTi me?  
 might return #510240xxx... (1024-byte data) as the results of the gated output power measurement under the cdma2000 reverse link standard.

**Related Commands** : INStrument[: SElect]

## :FETCh:*Standard*:SPECtrum:ACPower?

Fetches the spectrum waveform data of the ACPR measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K | RLCDMA2K: SPECtrum: ACPower?

**Arguments** None

**Returns** #<Num\_digi t><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digi t> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the spectrum amplitude in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.

n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: SPECtrum: ACPower?  
 might return #510240xxx... (1024-byte data) as the spectrum waveform data of the ACPR measurement under the cdma2000 forward link standard.

**Related Commands** : INStrument[: SElect]

## :FETCh:*Standard*:SPECtrum:CHPower?

Fetches the spectrum waveform data of the channel power measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K|RLCDMA2K: SPECtrum: CHPower?

**Arguments** None

**Returns** #<Num\_digi t><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digi t> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the spectrum amplitude in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.

n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: SPECtrum: CHPower?

might return #510240xxx... (1024-byte data) as the spectrum waveform data of the channel power measurement under the cdma2000 forward link standard.

**Related Commands** : INStrument[: SElect]

## :FETCh:*Standard*:SPECtrum:IM?

Fetches the spectrum waveform data of the intermodulation measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K|RLCDMA2K: SPECtrum: IM?

**Arguments** None

**Returns** #<Num\_digi t><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digi t> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the spectrum amplitude in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.  
n: Max 512000 (= 1024 points × 500 frames).

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: SPECtrum: IM?  
might return #510240xxx... (1024-byte data) as the spectrum waveform data of the intermodulation measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[: SElect]

## :FETCh:*Standard*:SPECtrum:OBWidth?

Fetches the spectrum waveform data of the occupied bandwidth measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : FETCh: FLCDMA2K | RLCDMA2K: SPECtrum: OBWi dth?

**Arguments** None

**Returns** #<Num\_digi t><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digi t> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the spectrum amplitude in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.

n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : FETCh: FLCDMA2K: SPECtrum: OBWi dth?  
might return #510240xxx... (1024-byte data) as the spectrum waveform data of the occupied bandwidth measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[: SElect]



# :MMEMory Commands

The :MMEMory commands allow you to manipulate files on the hard disk or floppy disk.

For details on file manipulation, refer to the *WCA230A & WCA280A Portable Wireless Communication Analyzers User Manual*.

## Command Tree

```
:MMEMory
  :LOAD
    :LIMit      <file_name>
  :STORE
    :LIMit      <file_name>
    :STABl e    <file_name>
```

### :MMEMory:LOAD:LIMit

Loads limits from the specified file.

**Syntax**      :MMEMory:LOAD:LIMit <file\_name>

**Arguments**    <file\_name> ::=<string> specifies the file from which to load limits.  
The file extension is .lmt.

**Measurement Modes**    DEMFLCDMA2K, DEMRLCDMA2K

**Examples**      :MMEMory:LOAD:LIMit "C:\My Documents\Test.lmt"  
loads limits from the file Test.lmt in the My Documents folder.

## :MMEMory:STORe:LIMit

Stores the current limits in the specified file.

**Syntax** : MMEMory: STORe: LIMit <file\_name>

**Arguments** <file\_name> ::= <string> specifies the file in which to store the current limits. The file extension is .lmt.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : MMEMory: STORe: LIMit "C:\My Documents\Test.lmt"  
stores the current limits in the file Test.lmt in the My Documents folder.

## :MMEMory:STORe:STABle

Stores the symbol table in the specified file.

**Syntax** : MMEMory: STORe: STABle <file\_name>

**Arguments** <file\_name> ::= <string> specifies the file in which to store the symbol table. The file is in text format, and its extension is .sym.

The following are written in the header before the data:

1. Data and time
2. Modulation
3. Symbol rate
4. Walsh code length
5. Walsh code number
6. PN offset (FLCDMA2K only)
7. PCG number
8. Time from the data end point of the first symbol.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : MMEMory: STORe: STABle "C:\My Documents\Data1.sym"  
stores the symbol table in the file Data1.sym in the My Documents folder.

# :READ Commands

The :READ commands acquire an input signal once in the single mode and obtain the measurement results from the data.

If you want to fetch the measurement results from the data currently residing in the memory without acquiring the input signal use the :FETCh commands on page 3-43.

---

**NOTE.** *Throughout the header descriptions in this section, the word **Standard** in italics is substituted for either of the following two measurement standards; FLCDMA2K (cdma2000 forward link) or RLCDMA2K (cdma2000 reverse link).*

---

## Command Tree

```
:READ
  :FLCDMA2K|RLCDMA2K
    :ACPower?
    :CCDF?
    :CHPower?
    :IM?
    :OBWidth?
    :PVTime?
    :SEMask?
    :DISTRibution
      :CCDF?
    :TAMPItude
      :PVTime?
    :SPECtrum
      :ACPower?
      :CHPower?
      :IM?
      :OBWidth?
```

---

**NOTE.** *There are no :READ subsystems for :CDPower?, :MACAccuracy?, and :PCCChannel? commands. These commands need to execute [:SENSe]:Standard [:IMMEDIATE] command in order to retrieve the measurement results.*

---

## :READ:*Standard*:ACPower?

Obtains the results of the ACPR measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : READ: FLCDMA2K|RLCDMA2K: ACPower?

**Arguments** None

**Returns** <Pass\_fail>, <Chpower>, <Acpr1>, <Acpr2>, <Acpr3>, <Acpr4>, <Acpr5>, <Acpr6>, <Acpr7>, <Acpr8>, <Acpr9>, <Acpr10>, <Acpr11>, <Acpr12>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

<Chpower> ::= <NRF> is the channel power measured value in dBm.

<Acpr1> ::= <NRF> is the first adjacent channel ACPR in dBc.

<Acpr2> ::= <NRF> is the second adjacent channel ACPR in dBc.

<Acpr3> ::= <NRF> is the third adjacent channel ACPR in dBc.

.

.

<Acpr10> ::= <NRF> is the tenth adjacent channel ACPR in dBc.

<Acpr11> ::= <NRF> is the eleventh adjacent channel ACPR in dBc.

<Acpr12> ::= <NRF> is the twelfth adjacent channel ACPR in dBc.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : READ: FLCDMA2K: ACPower?

might return 0, -2.045E+001, -6.461E+001, -4.379E+001, -6.576E+001, -6.753E+001, -6.79E+001, -1.0E+038, -1.0E+038, -1.0E+038, -1.0E+038, -1.0E+038, -1.0E+038 for the ACPR measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[:SELect]

## :READ:*Standard*:CCDF?

Obtains the results of the CCDF measurement under the cdma2000 forward link or reverse link standard.

**Syntax** :READ:FLCDMA2K|RLCDMA2K:CCDF?

**Arguments** None

**Returns** <Mean\_power>, <Peak\_power>, <Crest\_factor>

Where

<Mean\_power>::=<NRF> is the average power in dBm.

<Peak\_power>::=<NRF> is the peak power in dBm.

<Crest\_factor>::=<NRF> is the crest factor in dB.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :READ:FLCDMA2K:CCDF?

might return -2.043E+001, -9.75E+000, 1.068E+001 for the CCDF measurement under the cdma2000 forward link standard.

**Related Commands** :INSTRument[:SElect]

## :READ:*Standard*:CHPower?

Obtains the results of the channel power measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : READ: FLCDMA2K | RLCDMA2K: CHPower?

**Arguments** None

**Returns** <Pass\_fail>, <Chpower>, <Power\_densit>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

<Chpower> ::= <NRF> is the channel power measured value in dBm.

<Power\_densit> ::= <NRF> is the power density measured value in dBm/Hz.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : READ: FLCDMA2K: CHPower?

might return 1, -2.0375E+001, -8.1274E+001 for the channel power measurement under the cdma2000 forward link standard.

**Related Commands** : INSTRument[:SELect]

## :READ:*Standard*:IM?

Obtains the results of the intermodulation measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : READ: FLCDMA2K | RLCDMA2K: IM?

**Arguments** None

**Returns** <Pass\_fail>, <L\_channel>, <U\_channel>, <L3\_Lower>, <L3\_Upper>, <U3\_Lower>, <U3\_Upper>, <L5\_Lower>, <L5\_Upper>, <U5\_Lower>, <U5\_Upper>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

<L\_channel> ::= <NRF> is the lower channel measured value in dBm.

<U\_channel> ::= <NRF> is the upper channel measured value in dBm.

<L3\_Lower> ::= <NRF> is the lower third order (lower) measured value in dBc.

<L3\_Upper> ::= <NRF> is the lower third order (upper) measured value in dBc.

<U3\_Lower> ::= <NRF> is the upper third order (lower) measured value in dBc.

<U3\_Upper> ::= <NRF> is the upper third order (upper) measured value in dBc.

<L5\_Lower> : =<NRF> is the lower fifth order (lower) measured value in dBc.  
 <L5\_upper> : =<NRF> is the lower fifth order (upper) measured value in dBc.  
 <U5\_Lower> : =<NRF> is the upper fifth order (lower) measured value in dBc.  
 <U5\_upper> : =<NRF> is the upper fifth order (upper) measured value in dBc.

When each value is not present, the value of -1000 is returned.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :READ:FLCDMA2K:IM?  
 might return 1, -2.058E+001, -5.446E+001, -1.68E+001, 1.71E+001,  
 -4.76E+001, -1.37E+001, -4.73E+001, -1.34E+001, -5.11E+001, -1.72E+001  
 for the intermodulation measurement under the cdma2000 forward link standard.

**Related Commands** :INSTrument[:SElect]

## :READ:Standard:OBWidth?

Obtains the results of the occupied bandwidth measurement under the cdma2000 forward link or reverse link standard.

**Syntax** :READ:FLCDMA2K|RLCDMA2K:OBWidth?

**Arguments** None

**Returns** <Pass\_fail>, <obw>

Where

<Pass\_fail> : ={1|0} is the measurement result; 1: Pass or 0: Fail.  
 <obw> : =<NRF> is the measured value of the occupied bandwidth in Hz.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :READ:FLCDMA2K:OBWidth?  
 might return 1, 1.26763E+006 for the occupied bandwidth measurement results.

**Related Commands** :INSTrument[:SElect]

## :READ:RLCDMA2K:PVTi me?

Obtains the results of the gated output power measurement under the cdma2000 reverse link standard.

**Syntax** : READ: RLCDMA2K: PVTi me?

**Arguments** None

**Returns** <Pass\_fail>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

**Measurement Modes** DEMRLCDMA2K

**Examples** : READ: RLCDMA2K: PVTi me?

might return 1, indicating that the gated output power measurement has passed.

**Related Commands** : INSTRument[: SElect]

## :READ:*Standard*:SEMask?

Obtains the results of the spectrum emission mask measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : READ: FLCDMA2K | RLCDMA2K: SEMask?

**Arguments** None

**Returns** <Pass\_fail>

Where

<Pass\_fail> ::= {1|0} is the measurement result; 1: Pass or 0: Fail.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : READ: FLCDMA2K: SEMask?

might return 1, indicating that the spectrum emission mask measurement has passed.

**Related Commands** : INSTRument[: SElect]

## :READ:*Standard*:DISTribution:CCDF?

Obtains the distribution data of the CCDF measurement under the cdma2000 forward link or reverse link standard.

**Syntax** :READ:FLCDMA2K|RLCDMA2K:DISTribution:CCDF?

**Arguments** None

**Returns** #<Num\_digits><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the absolute power for each symbol in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.

n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :READ:FLCDMA2K:DISTribution:CCDF?

might return #510240xxx... (1024-byte data) as the results of the CCDF measurement under the cdma2000 forward link standard.

**Related Commands** :INSTRument[:SElect]

## :READ:RLCDMA2K:TAMPItude:PVTime?

Obtains the time domain amplitude data of the gated output power measurement under the cdma2000 reverse link standard.

**Syntax** : READ: RLCDMA2K: TAMPItude: PVTime?

**Arguments** None

**Returns** #<Num\_digits><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the absolute power for each symbol in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.

n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMRLCDMA2K

**Examples** : READ: FLCDMA2K: TAMPItude: PVTime?

might return #510240xxx... (1024-byte data) as the results of the gated output power measurement under the cdma2000 reverse link standard.

**Related Commands** : INSTRument[:SELect]

## :READ:*Standard*:SPECtrum:ACPower?

Obtains the spectrum waveform data of the ACPR measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : READ: FLCDMA2K|RLCDMA2K: SPECtrum: ACPower?

**Arguments** None

**Returns** #<Num\_digits><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digits> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the spectrum amplitude in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.  
n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :READ:FLCDMA2K:SPECtum:ACPower?  
might return #510240xxx... (1024-byte data) as the spectrum waveform data of the ACPR measurement under the cdma2000 forward link standard.

**Related Commands** :INSTRument[:SElect]

## :READ:*Standard*:SPECtum:CHPower?

Obtains the spectrum waveform data of the channel power measurement under the cdma2000 forward link or reverse link standard.

**Syntax** :READ:FLCDMA2K|RLCDMA2K:SPECtum:CHPower?

**Arguments** None

**Returns** #<Num\_digi\_t><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digi\_t> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the spectrum amplitude in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.

n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :READ:FLCDMA2K:SPECtum:CHPower?  
might return #510240xxx... (1024-byte data) as the spectrum waveform data of the channel power measurement under the cdma2000 forward link standard.

**Related Commands** :INSTRument[:SElect]

## :READ:*Standard*:SPECtrum:IM?

Obtains the spectrum waveform data of the intermodulation measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : READ: FLCDMA2K | RLCDMA2K: SPECtrum: IM?

**Arguments** None

**Returns** #<Num\_digi t><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digi t> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the spectrum amplitude in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.

n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** : READ: FLCDMA2K: SPECtrum: IM?

might return #510240xxx... (1024-byte data) as the spectrum waveform data of the intermodulation measurement under the cdma2000 forward link standard.

**Related Commands** : INStrument[: SElect]

## :READ:*Standard*:SPECtrum:OBWidth?

Obtains the spectrum waveform data of the occupied bandwidth measurement under the cdma2000 forward link or reverse link standard.

**Syntax** : READ: FLCDMA2K | RLCDMA2K: SPECtrum: OBWidth?

**Arguments** None

**Returns** #<Num\_digi t><Num\_byte><Data(1)><Data(2)>...<Data(n)>

Where

<Num\_digi t> is the number of digits in <Num\_byte>.

<Num\_byte> is the number of bytes of the data that follow.

<Data(n)> is the spectrum amplitude in dBm.

Four-byte little endian floating-point format specified IEEE 488.2.  
n: Max 512000 (= 1024 points × 500 frames)

Invalid data is returned as -1000.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :READ:FLCDMA2K:SPECTrum:OBWi dth?  
might return #510240xxx... (1024-byte data) as the spectrum waveform data of  
the occupied bandwidth measurement under the cdma2000 forward link standard.

**Related Commands** :INSTrument[:SElect]



# :SENSe Commands

---

**NOTE.** Throughout the header descriptions in this section, the word **Standard** in *italics* is substituted for either of the following two measurement standards; **FLCDMA2K** (*cdma2000 forward link*) or **RLCDMA2K** (*cdma2000 reverse link*).

---

The :SENSe commands set the details for each of the measurement sessions. They are divided into the following subgroups:

Table 3-17: :SENSe command subgroups

Command header	Function	Page number
<code>:SENSe]:Standard</code>	Set up the conditions related to the cdma2000 forward link or reverse link analysis.	Page 3-76
<code>:SENSe]:Standard:ACPower</code>	Set up ACPR measurement	Page 3-82
<code>:SENSe]:Standard:CCDF</code>	Set up CCDF measurement	Page 3-84
<code>:SENSe]:Standard:CDPower</code>	Set up code domain power measurement	Page 3-86
<code>:SENSe]:Standard:CHPower</code>	Set up channel power measurement	Page 3-92
<code>:SENSe]:Standard:IM</code>	Set up Intermodulation measurement	Page 3-95
<code>:SENSe]:Standard:MACAccuracy</code>	Set up modulation accuracy measurement	Page 3-99
<code>:SENSe]:Standard:OBWidth</code>	Set up occupied bandwidth measurement	Page 3-109
<code>:SENSe]:Standard:PCCHannel</code>	Set up pilot to code channel measurement	Page 3-110
<code>:SENSe]:RLCDMA2K:PVTIME</code>	Set up gated output power measurement	Page 3-117
<code>:SENSe]:Standard:SEMask</code>	Set up spectrum emission mask measurement	Page 3-121

## [:SENSe]:*Standard* Subgroup

The [:SENSe]:*Standard* commands set up the conditions related to the cdma2000 forward link or reverse link analysis.

<b>Command Tree</b>	<b>[: SENSe]</b>
	: FLCDMA2K   RLCDMA2K
	: ACQuisi ti on
	: CHIPs <numeric_value>
	: HIStory <numeric_value>
	: SEConds <numeric_value>
	: ANALysis
	: INTerval <numeric_value>
	: OFFSet <numeric_value>
	: BLOCK <numeric_value>
	[: IMMedi ate]
	: MEASurement CHPower   ACPower   IM   SEMask   CDPower   MACAccuracy   CCDF   PVTi me   PCCChannel   OBWid th   OFF
	: SPECtrum
	: OFFSet <numeric_value>
	: TINTerval

### [:SENSe]:*Standard*:ACQuisition:CHIPs (?)

Sets or queries the acquisition length in chips.

**Syntax**   [: SENSe]: FLCDMA2K | RLCDMA2K: ACQuisi ti on: CHIPs <numeric\_value>

[: SENSe]: FLCDMA2K | RLCDMA2K: ACQuisi ti on: CHIPs?

**Arguments**   <numeric\_value> : =<NR1> specifies the acquisition length in chips.  
Range: 6144 to no logical limitation (depends on Span and memory length).

**Measurement Modes**   DEMFLCDMA2K, DEMRLCDMA2K

**Examples**   [: SENSe: FLCDMA2K: ACQuisi ti on: CHIPs 10240  
sets the acquisition length in chips to 10240 in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:ACQuisition:HISTory (?)

Sets or queries the acquisition history. The acquisition can be viewed as it is selected, and can be reanalyzed after the selection.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:ACQuisition:HISTORY <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:ACQuisition:HISTORY?

**Arguments** <numeric\_value> ::= <NR1> specifies the acquisition history.  
Range: No logical limitation to 0 (depends on Span and memory length).

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:ACQuisition:HISTORY 0  
sets the acquisition history to 0 in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:ACQuisition:SEConds (?)

Sets or queries the acquisition length in seconds.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:ACQuisition:SECONDS <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:ACQuisition:SECONDS?

**Arguments** <numeric\_value> ::= <NRF> specifies the acquisition length in seconds.  
Range: 4.998 ms to no logical limitation (depends on Span and memory length).

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:ACQuisition:SECONDS 9.163ms  
sets the acquisition length in seconds to 9.163 ms in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:ANALysis:INTerval (?)

Sets or queries the analysis interval in chips.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:ANALysi s: INTerval <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:ANALysi s: INTerval ?

**Arguments** <numeric\_value>: :=<NR1> specifies the analysis interval in chips.

The range depends on the acquisition length setting.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:ANALysi s: INTerval 3072

sets the analysis interval in chips to 3072 in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:ANALysis:OFFSet (?)

Sets or queries the analysis offset (the start point of the analysis range) in chips.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:ANALysi s: OFFSet <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:ANALysi s: OFFSet?

**Arguments** <numeric\_value>: :=<NR1> specifies the analysis offset in chips.

Range: 0 to 12582912 chips.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:ANALysi s: OFFSet 512

sets the analysis offset in chips to 512 in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:BLOCK (?)

Sets or queries the number of the block to measure in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:BLOCK <numer i c\_val ue>

[:SENSe]:FLCDMA2K|RLCDMA2K:BLOCK?

**Arguments** <numer i c\_val ue> ::= <NR1> specifies the block number. Zero represents the latest block.  
Range: -M to 0 (M: number of acquired blocks).

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:BLOCK -5  
sets the block number to -5 in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*[:IMMediate]

Performs calculation for the acquired data in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K[:IMMediate]

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:IMMediate  
performs calculation for the acquired data in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:MEASurement (?)

Selects or queries the measurement item for the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K: MEASurement {CHPower|ACPower|IM|SEMask|CDPower|MACCuracy|CCDF|PVTime|PCCHannel|OBWidth|OFF}

[:SENSe]:FLCDMA2K|RLCDMA2K: MEASurement?

**Arguments** The arguments and measurement items are listed below:

Argument	Measurement item
CHPower	Channel power measurement
ACPower	ACPR measurement
IM	Intermodulation measurement
SEMask	Spectrum emission mask measurement
CDPower	Code domain power measurement
MACCuracy	Modulation accuracy measurement
CCDF	CCDF measurement
PVTime*	Gated output power measurement
PCCHannel	Pilot to code channel measurement
OBWidth	Occupied bandwidth measurement
OFF	Measurement OFF

\* Only available when RLCDMA2K is selected.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K: MEASurement CCDF  
selects the CCDF measurement for the cdma2000 forward link analysis.

**[:SENSe]:Standard:SPECtrum:OFFSet (?)**

Sets or queries the spectrum offset within the time window in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SPECtrum:OFFSet <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:SPECtrum:OFFSet?

**Arguments** <numeric\_value> ::= <NRf> specifies the spectrum offset within the time windows.  
Range: 0 ms to 26.56 ms.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SPECtrum:OFFSet 10ms  
sets the spectrum offset within the time window to 10 ms in the cdma2000 forward link analysis.

**[:SENSe]:Standard:SPECtrum:TINTerval?**

Queries the length of the time-domain information used to construct the spectrum trace in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SPECtrum:TINTerval ?

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SPECtrum:TINTerval ?  
returns the length of the time-domain information in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:ACPower Subgroup

The [:SENSe]:*Standard*:ACPower commands set up the conditions related to the ACPR measurement in the cdma2000 forward link or reverse link analysis.

**Command Tree**

```
[:SENSe]
  :FLCDMA2K|RLCDMA2K
  :ACPower
    :BANDwidth|BWIDth
      :INTegration <numeric_value>
    :FILT
      :COEFFicient <numeric_value>
      :TYPE RECTangle|GAUSSian|NYquist|RNYquist
    :LIMit
      :ADJacent[1]|2|3..|12
      [:STATE] <boolean>
```

## [:SENSe]:*Standard*:ACPower:BANDwidth|BWIDth:INTegration (?)

Sets or queries the bandwidth of the main channel for the ACPR measurement in the cdma2000 forward link or reverse link analysis.

**Syntax**      [:SENSe]:FLCDMA2K|RLCDMA2K:ACPower:BANDwidth|BWIDth:INTegration  
                  <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:ACPower:BANDwidth|BWIDth:INTegration?

**Arguments**     <numeric\_value>: :=<NRF> specifies the bandwidth of the main channel for the ACPR measurement. Range: Span/20 to full span [Hz].

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples**      :SENSe:FLCDMA2K:ACPower:BANDwidth:INTegration 2.5MHz  
sets the bandwidth of the main channel to 2.5 MHz in the cdma2000 forward link analysis.

## [:SENSe]:Standard:ACPower:FILTter:COEFFficient (?)

Sets or queries the filter roll-off rate for the ACPR measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:ACPower:FILTter:COEFFficient  
<numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:ACPower:FILTter:COEFFficient?

**Arguments** <numeric\_value>::=<NRF> specifies the roll-off rate.  
Range: 0 to 1.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:ACPower:FILTter:COEFFficient 0.5  
sets the filter roll-off rate for the ACPR measurement to 0.5 in the cdma2000 forward link analysis.

## [:SENSe]:Standard:ACPower:FILTter:TYPE (?)

Select or queries the filter for the ACPR measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:ACPower:FILTter:TYPE {RECTangle  
|GAUSSian|NYQuist|RNYQuist}

[:SENSe]:FLCDMA2K|RLCDMA2K:ACPower:FILTter:TYPE?

**Arguments** The arguments and filters are listed below:

Argument	Filter
RECTangle	Rectangular
GAUSSian	Gaussian
NYQuist	Nyquist
RNYQuist	Root Nyquist

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:ACPower:FILTter:TYPE NYQuist  
selects the Nyquist filter for the ACPR measurement in the cdma2000 forward link analysis.

## [**:SENSe**]:*Standard*:ACPower:LIMit:ADJacent[1]|2|3..|12[:STATe] (?)

Sets or queries whether to enable or disable the adjacent limit testing for the ACPR measurement in the cdma2000 forward link or reverse link analysis.

**Syntax**    [:SENSe]:FLCDMA2K|RLCDMA2K:ACPower:LIMit:ADJacent[1]|2|3..|12  
[:STATe] {ON|OFF|1|0}

[:SENSe]:FLCDMA2K|RLCDMA2K:ACPower:LIMit:ADJacent[1]|2|3..|12  
[:STATe]?

ADJacent [1]|2|3..|12 is defined as follows:

ADJacent[1]: first adjacent  
ADJacent2: second adjacent  
ADJacent3: third adjacent

ADJacent12: twelfth adjacent

**Arguments**    ON or 1 enables the adjacent limit testing.  
OFF or 0 disables the adjacent limit testing.

**Measurement Modes**    DEMFLCDMA2K, DEMRLCDMA2K

**Examples**    :SENSe:FLCDMA2K:ACPower:LIMit:ADJacent1 ON  
enables the first adjacent limit testing for the ACPR measurement in the cdma2000 forward link analysis.

## [**:SENSe**]:*Standard*:CCDF Subgroup

The [:SENSe]:*Standard*:CCDF commands set up the conditions related to the CCDF measurement in the cdma2000 forward link or reverse link analysis.

**Command Tree**

```
[:SENSe]
  :FLCDMA2K|RLCDMA2K
  :CCDF
    :RMESurement
    :THReshol d      <numeric_value>
```

## [:SENSe]:Standard:CCDF:RMEasurement

Clears the CCDF accumulator and restarts the measurement.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CCDF:RMEasurement

**Arguments** None

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CCDF:RMEasurement  
clears the CCDF accumulator and restart the measurement for the CCDF measurement in the cdma2000 forward link analysis.

## [:SENSe]:Standard:CCDF:THreshold (?)

Sets or queries the threshold for the CCDF measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CCDF:THreshold <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:CCDF:THreshold?

**Arguments** <numeric\_value> ::= <NRF> specifies the threshold for the CCDF measurement.  
Range: -250 dBm to 130 dBm.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CCDF:THreshold -100dBm  
sets the threshold for the CCDF measurement to -100 dBm in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:CDPower Subgroup

The [:SENSe]:*Standard*:CDPower commands set up the conditions related to the code domain power measurement in the cdma2000 forward link or reverse link analysis.

<b>Command Tree</b>	[:SENSe]	
	:FLCDMA2K RLCDMA2K	
	:CDPower	
	:ACCThreshold	<numeric_value>
	:FILT	
	:MEASurement	OFF EQComp COMP
	:IQSwap	<boolean>
	:MLEvel	CHIP SYMBOL
	:PNOFFset	<numeric_value>
	:QOF	<numeric_value>
	:RConfig	<string>
	:SELect	
	:CODE	<numeric_value>
	:PCG	<numeric_value>
	:WCODE	COMPOSITE W2L W4L W8L W16L  W32L W64L W128L

### [:SENSe]:*Standard*:CDPower:ACCThreshold (?)

Sets or queries the active channel threshold level (in dB from the pilot), which is used for deciding whether a code channel is active or inactive, for the code domain power measurement in the cdma2000 forward link or reverse link analysis.

**Syntax**   [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:ACCThreshold <numeric\_value>

         [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:ACCThreshold?

**Arguments**   <numeric\_value> ::=<NRF> specifies the active channel threshold level.  
Range: -50 dB to 50 dB.

**Measurement Modes**   DEMFLCDMA2K, DEMRLCDMA2K

**Examples**   [:SENSe]:FLCDMA2K:CDPower:ACCThreshold -27dB  
sets the active channel threshold level to -27 dB for the code domain power measurement in the cdma2000 forward link analysis.

## [:SENSe]:Standard:CDPower:FILTter:MEASurement (?)

Selects or queries the measurement filter for the code domain power measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:FILTter:MEASurement  
 {OFF|EQComp|COMP}

[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:FILTter:MEASurement?

**Arguments**

OFF	specifies that no measurement filter is used.
EQComp	selects the Complementary filter + EQ (equalizer).
COMP	selects the Complementary filter.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CDPower:FILTter:MEASurement COMP  
 selects the Complementary filter for the code domain power measurement in the cdma2000 forward link analysis.

## [:SENSe]:Standard:CDPower:IQSWap (?)

Sets or queries whether to enable or disable IQ swapping for the code domain power measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:IQSWap <bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:IQSWap?

**Arguments**

<bool ean>::= {ON OFF 1 0}
ON or 1 enables the IQ swapping.
OFF or 0 disables the IQ swapping.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CDPower:IQSWap ON  
 sets the IQ swapping to ON for the code domain power measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:CDPower:MLEVel (?)

Sets or queries the measurement level for the code domain power measurement in the cdma2000 forward link or reverse link analysis. This command is only available when the :DISPlay:*Standard*:DDEMod:MView:FORMat command is set to IQPower.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:MLEVel {CHIP|SYMBOL}

[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:MLEVel ?

**Arguments** CHIP symbol level  
SYMBOL chip level

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CDPower:MLEVel CHIP  
sets the measurement level to chip for the code domain power measurement in the cdma2000 forward link analysis.

**Related Commands** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:VIEW:FORMAT

## [:SENSe]:FLCDMA2K:CDPower:PNOffset (?)

Sets or queries the PN offset for the code domain power measurement in the cdma2000 forward link analysis.

**Syntax** [:SENSe]:FLCDMA2K:CDPower:PNOffset <numerical\_value>

[:SENSe]:FLCDMA2K:CDPower:PNOffset?

**Arguments** <numerical\_value>: :=<NR1> specifies the PN offset in the unit of 64 chips.  
Range: 0 to 511.

**Measurement Modes** DEMFLCDMA2K

**Examples** :SENSe:FLCDMA2K:CDPower:PNOffset 100  
sets the PN offset to 100 for the code domain power measurement in the cdma2000 forward link analysis.

## [:SENSe]:FLCDMA2K:CDPower:QOF (?)

Sets or queries the Walsh code quasi-orthogonal function for the code domain power measurement in the cdma2000 forward link analysis. This command is only available when :DISPlay:Standard:DDEMod:MVlew:FORMat command is set to CDPower or PCGRam and the [:SENSe]:Standard:CDPower:MLEVel command is set to SYMBol.

**Syntax** [:SENSe]:FLCDMA2K:CDPower:QOF <numer ic\_val ue>

[:SENSe]:FLCDMA2K:CDPower:QOF?

**Arguments** <numer ic\_val ue> ::=<NR1> specifies the Walsh code quasi-orthogonal function. Range: 0 to 3.

**Measurement Modes** DEMFLCDMA2K

**Examples** :SENSe:FLCDMA2K:CDPower:QOF 1  
sets the Walsh code quasi-orthogonal function to 1 for the code domain power measurement in the cdma2000 forward link analysis.

**Related Commands** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MVlew:FORMat,  
[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:MLEVel

## [:SENSe]:Standard:CDPower:RConfig (?)

Selects or queries the available radio configuration for the code domain power measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:RConfig <string>

[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:RConfig?

**Arguments** <string> ::= {"CDMAONE" | "CDMA2K1X"}  
"CDMAONE" selects RC1/RC2 for FLCDMA2K.  
"CDMA2K1X" selects RC3/RC4/RC5 for FLCDMA2K and RC3/RC4 for RLCDMA2K.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CDPower:RConfig "CDMAONE"  
sets the radio configuration to RC1/RC2 for the code domain power measurement in the cdma2000 forward link analysis.

## [{:SENSe}]:*Standard*:CDPower:SElect:CODE (?)

Sets or queries the code in the PCG for the code domain power measurement in the cdma2000 forward link or reverse link analysis. This command is only available when the :DISPlay:*Standard*:DDEMod:MView:FORMat command is set to IQPower, CDPower, or PCGram. For IQPower, when the [:SENSe]:*Standard*:CDPower:MLEVel command is set to CHIP, the argument value is fixed to 0.

**Syntax**      [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:SElect:CODE <numer ic\_val ue>  
[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:SElect:CODE?

**Arguments**    <numer ic\_val ue>: =<NR1> specifies the code in the PCG.  
The available ranges are as follows:

- **FLCDMA2K:**  
64 fixed when the [:SENSe]:*Standard*:CDPower:RConfig command is set to “CDMAONE”  
4 to 128 when the [:SENSe]:*Standard*:CDPower:RConfig command is set to “CDMA2K1X”
- **RLCDMA2K:**  
2 to 64 when the [:SENSe]:*Standard*:CDPower:RConfig command is set to “CDMA2K1X”

**Measurement Modes**    DEMFLCDMA2K, DEMRLCDMA2K

**Examples**      :SENSe:FLCDMA2K:CDPower:SElect:CODE 30  
sets the code in the PCG to 30 for the code domain power measurement in the cdma2000 forward link analysis.

**Related Commands**    :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MView:FORMat,  
[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:MLEVel  
[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:RConfig

## [:SENSe]:*Standard*:CDPower:SElect:PCG (?)

Sets or queries the PCG (power control group) for the code domain power measurement in the cdma2000 forward or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:SElect:PCG <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:SElect:PCG?

**Arguments** <numeric\_value> ::= <NR1> specifies the PCG.  
Range: -(number of analyzed chips -1) to 0.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CDPower:SElect:PCG -10  
sets the PCG to -10 for the code domain power measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:CDPower:WCODe (?)

Selects or queries the Walsh code length for the code domain power measurement in the cdma2000 forward link or reverse link analysis. This command is only available when the [:SENSe]:*Standard*:CDPower:RConfig command is set to CDMA2K1X.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:WCODe {COMPosite|W2L|W4L|W8L|W16L|W32L|W64L|W128L}

[:SENSe]:FLCDMA2K|RLCDMA2K:CDPower:WCODe?

**Arguments** The arguments and lengths are listed below:

Argument	Length
COMPosite	composite
W2L <sup>1</sup>	2
W4L	4
W8L	8
W16L	16
W32L	32
W64L	64
W128L <sup>2</sup>	128

1 This argument is only available in the RLCDMA2K standard.

2 This argument is only available in the FLCDMA2K standard.

<b>Measurement Modes</b>	DEMFLCDMA2K, DEMRLCDMA2K
<b>Examples</b>	:SENSe:FLCDMA2K:CDPower:WCODe W4L sets the Walsh code length to 4 for the code domain power measurement in the cdma2000 forward link analysis.
<b>Related Commands</b>	[:SENSe]:FLCDMA2K RLCDMA2K:CDPower:RConfig

## [:SENSe]:*Standard*:CHPower Subgroup

The [:SENSe]:*Standard*:CHPower commands set up the conditions related to the channel power measurement in the cdma2000 forward link or reverse link analysis.

<b>Command Tree</b>	[:SENSe] :FLCDMA2K RLCDMA2K :CHPower :BANDwidth BWIDth :INTegration <numerical_value> :FILTter :COEFFicient <numerical_value> :TYPE RECTangle GAUSSian NYquist RNYquist :LIMit [:STATe] <boolean>
---------------------	--

## [:SENSe]:*Standard*:CHPower:BANDwidth|BWIDth:INTegration (?)

Sets or queries the channel bandwidth for the channel power measurement in the cdma2000 forward link or reverse link analysis.

<b>Syntax</b>	[:SENSe]:FLCDMA2K RLCDMA2K:CHPower:BANDwidth BWIDth:INTegration <numerical_value>
	[:SENSe]:FLCDMA2K RLCDMA2K:CHPower:BANDwidth BWIDth:INTegration?
<b>Arguments</b>	<numerical_value>: :=<NRF> specifies the channel bandwidth for the channel power measurement. Range: Span/20 to full span [Hz].
<b>Measurement Modes</b>	DEMFLCDMA2K, DEMRLCDMA2K
<b>Examples</b>	:SENSe:FLCDMA2K:CHPower:BANDwidth:INTegration 2.5MHz sets the channel bandwidth to 2.5 MHz for the channel power measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:CHPower:FILTter:COEFFcient (?)

Sets or queries the filter roll-off rate for the channel power measurement in the cdma2000 forward link or reverse link analysis. This command is only available when NYQuist or RNYQuist is selected in the [:SENSe]:*Standard*:CHPower:FILTter:TYPE command.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CHPower:FILTter:COEFFcient  
<numer ic\_val ue>

[:SENSe]:FLCDMA2K|RLCDMA2K:CHPower:FILTter:COEFFcient?

**Arguments** <numer ic\_val ue>::=<NRF> specifies the roll-off rate.  
Range: 0.0001 to 1 (default: 0.5).

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CHPower:FILTter:COEFFcient 0.1  
sets the filter roll-off rate to 0.1 for the channel power measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:CHPower:FILTter:TYPE (?)

Select or queries the filter for the channel power measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CHPower:FILTter:TYPE {RECTangle  
|GAUSSian|NYQuist|RNYQuist}

[:SENSe]:FLCDMA2K|RLCDMA2K:CHPower:FILTter:TYPE?

**Arguments** The arguments and filters are listed below:

Argument	Filter
RECTangle	Rectangular
GAUSSian	Gaussian
NYQuist	Nyquist
RNYQuist	Root Nyquist

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CHPower:FILTter:TYPE NYQuist  
selects the Nyquist filter for the channel power measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:CHPower:LIMit[:STATe] (?)

Sets or queries whether to enable or disable the limit testing for the channel power measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:CHPower:LIMit[:STATe] {ON|OFF|1|0}

[:SENSe]:FLCDMA2K|RLCDMA2K:CHPower:LIMit[STATe]?

**Arguments** ON or 1 enables the limit testing.  
OFF or 0 disables the limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:CHPower:LIMit:STATe ON  
enables the limit testing for the channel power measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:IM Subgroup

The [:SENSe]:*Standard*:IM commands set up the conditions related to the intermodulation measurement in the cdma2000 forward link or reverse link analysis.

<b>Command Tree</b>	[:SENSe]
	:FLCDMA2K RLCDMA2K
	:IM
	:BANDwidth BWIDth
	:INTegration <numeric_value>
	:FILTter
	:COEFFicient <numeric_value>
	:TYPE RECTangle GAUssian NYquist RNYquist
	:LIMIT
	:FORDer
	[:STATE] <boolean>
	:TORDer
	[:STATE] <boolean>
	:SCOffset <numeric_value>

### [:SENSe]:*Standard*:IM:BANDwidth|BWIDth:INTegration (?)

Sets or queries the channel bandwidth for the intermodulation measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:IM:BANDwidth|BWIDth:INTegration  
<numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:IM:BANDwidth|BWIDth:INTegration?

**Arguments** <numeric\_value> : = <NRF> specifies the bandwidth of the main channel for the intermodulation measurement. Range: Span/20 to full span [Hz].

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:IM:BANDwidth:INTegration 2.5MHz  
sets the channel bandwidth to 2.5 MHz for the intermodulation measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:IM:FILT<sub>r</sub>:COEFFicient (?)

Sets or queries the filter roll-off rate for the intermodulation measurement in the cdma2000 forward link or reverse link analysis. This command is only available when NYQuist or RNYQuist is selected in the [:SENSe]:*Standard*:IM:FILT<sub>r</sub>:TYPE command.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:IM:FILT<sub>r</sub>:COEFFicient <numerical\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:IM:FILT<sub>r</sub>:COEFFicient?

**Arguments** <numerical\_value> : =<NRF> specifies the roll-off rate.  
Range: 0.0001 to 1 (default: 0.5).

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** [:SENSe]:FLCDMA2K:IM:FILT<sub>r</sub>:COEFFicient 0.1  
sets the filter roll-off rate to 0.1 for the intermodulation measurement in the cdma2000 forward link analysis.

**Related Commands** [:SENSe]:FLCDMA2K|RLCDMA2K:IM:FILT<sub>r</sub>:TYPE

## [:SENSe]:*Standard*:IM:FILT<sub>r</sub>:TYPE (?)

Select or queries the filter for the intermodulation measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:IM:FILT<sub>r</sub>:TYPE {RECTangle|GAUssian|NYQuist|RNYQuist}

[:SENSe]:FLCDMA2K|RLCDMA2K:IM:FILT<sub>r</sub>:TYPE?

**Arguments** The arguments and filters are listed below:

Argument	Filter
RECTangle	Rectangular
GAUssian	Gaussian
NYQuist	Nyquist
RNYQuist	Root Nyquist

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:IM:FILT<sub>er</sub>:TYPE NYQui st  
 selects the Nyquist filter for the intermodulation measurement in the cdma2000 forward link analysis.

## [:SENSe]:Standard:IM:LIMit:FORDer[:STATe] (?)

Sets or queries whether to enable or disable the fifth order limit testing for the intermodulation measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:IM:LIMit:FORDer[:STATe] <bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:IM:LIMit:FORDer[:STATe]?

**Arguments** <bool ean> ::= {ON|OFF|1|0}  
 ON or 1 enables the fifth order limit testing.  
 OFF or 0 disables the fifth order limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:IM:LIMit:FORDer:STATe ON  
 enables the fifth order limit testing for the intermodulation measurement in the cdma2000 forward link analysis.

## [{:SENSe}]:*Standard*:IM:LIMit:TORDer[:STATe] (?)

Sets or queries whether to enable or disable the third order limit testing for the intermodulation measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:IM:LIMi t:TORDer[:STATe] <bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:IM:LIMi t:TORFer[:STATe]?

**Arguments** <bool ean>: :={ON|OFF|1|0}

ON or 1 enables the third order limit testing.

OFF or 0 disables the third order limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:IM:LIMi t:TORDer:STATe ON  
enables the third order limit testing for the intermodulation measurement in the cdma2000 forward link analysis.

## [{:SENSe}]:*Standard*:IM:SCOffset (?)

Sets or queries the second channel frequency for the intermodulation measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:IM:SCOffset <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:IM:SCOffset?

**Arguments** <numeric\_value>: :=<NRF> specifies the second channel frequency for the intermodulation. Range: -span/2 to +span/2 [Hz].

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:IM:SCOffset 1.5MHz  
sets the second channel frequency to 1.5 MHz for the intermodulation measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:MACCuracy Subgroup

The [:SENSe]:*Standard*:MACCuracy commands set up the conditions related to the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

Command Tree	[:SENSe]
	:FLCDMA2K RLCDMA2K
	:MACCuracy
	:ACCThreshold <numeric_value>
	:FILTter
	:MEASurement OFF EQComp COMP
	:IQSWAap <boolean>
	:LIMit
	:EVM
	:PEAK
	[:STATe] <boolean>
	:RMS
	[:STATe] <boolean>
	:PCDerror
	[:STATe] <boolean>
	:RHO
	[:STATe] <boolean>
	:TAU
	[:STATe] <boolean>
	:MLEVel CHIP SYMBOL
	:PNOFFset <numeric_value>
	:QOF <numeric_value>
	:RConfig <string>
	:SELect
	:CODE <numeric_value>
	:PCG <numeric_value>
	:WCODE COMPOSITE W2L W4L W8L W16L W32L W64L W128L

## [:SENSe]:*Standard*:MACCuracy:ACCThreshold (?)

Sets or queries the active channel threshold level (in dB from the pilot), which is used for deciding whether a code channel is active or inactive, for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:ACCThreshold <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:ACCThreshold?

**Arguments** <numeric\_value> ::= <NRF> specifies the active channel threshold level.  
Range: -50 dB to 50 dB.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:ACCThreshold -100  
sets the active channel threshold level to -100 dB for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:MACCuracy:FILTter:MEASurement (?)

Selects or queries the measurement filter for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K:MACCuracy:FILTter:MEASurement {OFF|EQComp|COMP}

[:SENSe]:FLCDMA2K:MACCuracy:FILTter:MEASurement?

**Arguments** OFF specifies that no measurement filter is used.  
EQComp selects the Complementary filter + EQ (equalizer).  
COMP selects the Complementary filter.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:FILTter:MEASurement COMP  
selects the Complementary filter for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [:SENSe]:Standard:MACCuracy:IQSWap (?)

Sets or queries whether to enable or disable IQ swapping for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:IQSWap <bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:IQSWap?

**Arguments** <bool ean> ::= {ON|OFF|1|0}  
ON or 1 enables the IQ swapping.  
OFF or 0 disables the IQ swapping.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:IQSWap ON  
sets the IQ swapping to ON for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [:SENSe]:Standard:MACCuracy:LIMit:EVM:PEAK[:STATe] (?)

Sets or queries whether to enable or disable the PEAK EVM limit checking for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:LIMit:EVM:PEAK[:STATe]  
<bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:LIMit:EVM:PEAK[:STATe]?

**Arguments** <bool ean> ::= {ON|OFF|1|0}  
ON or 1 enables the PEAK EVM limit testing.  
OFF or 0 disables the PEAK EVM limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:LIMit:EVM:PEAK:STATe ON  
enables the PEAK EVM limit testing for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [**:SENSe**]:*Standard*:MACCuracy:LIMit:EVM:RMS[:STATe] (?)

Sets or queries whether to enable or disable the RMS EVM limit testing for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:LIMit:EVM:RMS[:STATe]  
<bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:LIMit:EVM:RMS[:STATe]?

**Arguments** <bool ean>: :={ON|OFF|1|0}  
ON or 1 enables the RMS EVM limit testing.  
OFF or 0 disables the RMS EVM limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:LIMit:EVM:RMS:STATe ON  
enables the RMS EVM limit testing for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [**:SENSe**]:*Standard*:MACCuracy:LIMit:PCDerror[:STATe] (?)

Sets or queries whether to enable or disable the peak code domain error limit testing for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:LIMit:PCDerror[:STATe]  
<bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:LIMit:PCDerror[:STATe]?

**Arguments** <bool ean>: :={ON|OFF|1|0}  
ON or 1 enables the peak code domain error limit testing.  
OFF or 0 disables the peak code domain error limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:LIMit:PCDerror:STATe ON  
enables the peak code domain error limit testing for the modulation accuracy measurement in the cdma2000 forward link analysis.

**[:SENSe]:Standard:MACCuracy:LIMit:RHO[:STATe] (?)**

Sets or queries whether to enable or disable the Rho limit testing for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:LIMit:RHO[:STATe] <bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:LIMit:RHO[:STATe]?

**Arguments** <bool ean> ::= {ON|OFF|1|0}

ON or 1 enables the Rho limit testing.

OFF or 0 disables the Rho limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:LIMit:RHO:STATe ON

enables the Rho limit testing for the modulation accuracy measurement in the cdma2000 forward link analysis.

**[:SENSe]:FLCDMA2K:MACCuracy:LIMit:TAU[:STATe] (?)**

Sets or queries whether to enable or disable the Tau limit testing for the modulation accuracy measurement in the cdma2000 forward link analysis.

**Syntax** [:SENSe]:FLCDMA2K:MACCuracy:LIMit:TAU[:STATe] <bool ean>

[:SENSe]:FLCDMA2K:MACCuracy:LIMit:TAU[:STATe]?

**Arguments** <bool ean> ::= {ON|OFF|1|0}

ON or 1 enables the Tau limit testing.

OFF or 0 disables the Tau limit testing.

**Measurement Modes** DEMFLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:LIMit:TAU:STATe ON

enables the Tau limit testing for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:MACCuracy:MLEVel (?)

Sets or queries the measurement level for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:MLEVel {CHIP|SYMBOL}

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:MLEVel ?

**Arguments** CHIP chip level  
SYMBOL symbol level

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:MLEVel CHIP  
sets the measurement level to CHIP for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [:SENSe]:FLCDMA2K:MACCuracy:PNOFFset (?)

Sets or queries the PN offset for the modulation accuracy measurement in the cdma2000 forward link analysis.

**Syntax** [:SENSe]:FLCDMA2K:MACCuracy:PNOFFset <numerical\_value>

[:SENSe]:FLCDMA2K:MACCuracy:PNOFFset?

**Arguments** <numerical\_value> ::= <NR1> specifies the PN offset.  
Range: 0 to 511.

**Measurement Modes** DEMFLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:PNOFFset 100  
sets the PN offset to 100 for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [:SENSe]:FLCDMA2K:MACCuracy:QOF (?)

Sets or queries the Walsh code quasi-orthogonal function for the modulation accuracy measurement in the cdma2000 forward link analysis. This command is only available when :DISPlay:Standard:DDEMod:MView:FORMAT command is set to MACCuracy and the [:SENSe]:Standard:MACCuracy:MLEVel command is set to SYMBol.

**Syntax** [:SENSe]:FLCDMA2K:MACCuracy:QOF <numerical\_value>

[:SENSe]:FLCDMA2K:MACCuracy:QOF?

**Arguments** <numerical\_value> ::= <NR1> specifies the Walsh code quasi-orthogonal function. Range: 0 to 3.

**Measurement Modes** DEMFLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:QOF 1  
sets the Walsh code quasi-orthogonal function to 1 for the modulation accuracy measurement in the cdma2000 forward link analysis.

**Related Commands** :DISPlay:FLCDMA2K|RLCDMA2K:DDEMod:MView:FORMAT,  
[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:MLEVel

## [:SENSe]:Standard:MACCuracy:RConfig (?)

Selects or queries the available radio configuration for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:RConfig <string>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:RConfig?

**Arguments** <string> ::= {"CDMAONE" | "CDMA2K1X"}  
"CDMAONE" selects RC1/RC2 for FLCDMA2K and RLCDMA2K.  
"CDMA2K1X" selects RC3/RC4/RC5 for FLCDMA2K and RC3/RC4 for RLCDMA2K.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:RConfig "CDMAONE"  
sets the radio configuration to RC1/RC2 for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:MACCuracy:SElect:CODE (?)

Sets or queries the code in the PCG for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis. This command is only available when [:SENSe]:*Standard*:MACCuracy:MLEVel command is set to SYMBol.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:SElect:CODE <numer ic\_val ue>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:SElect:CODE?

**Arguments** <numer ic\_val ue> : =<NR1> specifies the code in the PCG.  
The available ranges are as follows:

- **FLCDMA2K:**  
64 fixed when the [:SENSe]:*Standard*:MACCuracy:RConfig command is set to “CDMAONE”  
4 to 128 when the [:SENSe]:*Standard*:MACCuracy:RConfig command is set to “CDMA2K1X”
- **RLCDMA2K:**  
2 to 64 when the [:SENSe]:*Standard*:MACCuracy:RConfig command is set to “CDMA2K1X”

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:SElect:CODE 30  
sets the code in the PCG to 30 for the modulation accuracy measurement in the cdma2000 forward link analysis.

**Related Commands** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:MLEVel  
[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:RConfig

## [:SENSe]:*Standard*:MACCuracy:SElect:PCG (?)

Sets or queries the PCG for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:SElect:PCG <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:MACCuracy:SElect:PCG?

**Arguments** <numeric\_value> ::= <NR1> specifies the PCG.  
Range: -(number of analyzed half slots -1) to 0.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:MACCuracy:SElect:PCG -10  
sets the PCG to -10 for the modulation accuracy measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:MACCuracy:WCODe (?)

Selects or queries the Walsh code length for the modulation accuracy measurement in the cdma2000 forward link or reverse link analysis. This command is only available when the [:SENSe]:*Standard*:MACCuracy:RCONfig command is set to CDMA2K1X.

### Syntax

[: SENSe]: FLCDMA2K | RLCDMA2K: MACCuracy: WCODe {COMPosi te|W2L|W4L|W8L|W16L|W32L|W64L|W128L}

[: SENSe]: FLCDMA2K | RLCDMA2K: MACCuracy: WCODe?

### Arguments

The arguments and lengths are listed below:

Argument	Length
COMPosi te	composite
W2L <sup>1</sup>	2
W4L	4
W8L	8
W16L	16
W32L	32
W64L	64
W128L <sup>2</sup>	128

- 1 This argument is only available in the RLCDMA2K standard.  
2 This argument is only available in the FLCDMA2K standard.

### Measurement Modes

DEMFLCDMA2K, DEMRLCDMA2K

### Examples

: SENSe: FLCDMA2K: MACCuracy: WCODe W4L

sets the Walsh code length to 4 for the modulation accuracy measurement in the cdma2000 forward link analysis.

### Related Commands

[: SENSe]: FLCDMA2K | RLCDMA2K: MACCuracy: RCONfi g

## [:SENSe]:*Standard*:OBWidth Subgroup

The [:SENSe]:*Standard*:OBWidth commands set up the conditions related to the occupied bandwidth (OBW) measurement in the cdma2000 forward link or reverse link analysis.

<b>Command Tree</b>	[:SENSe]
	:FLCDMA2K RLCDMA2K
	:OBWidth
	:LIMit
	[:STATe] <boolean>
	:PERCent <numeric_value>

### [:SENSe]:*Standard*:OBWidth:LIMit[:STATe] (?)

Sets or queries whether to enable or disable the limit testing for the OBW measurement in the cdma2000 forward link or reverse link analysis.

**Syntax**   [:SENSe]:FLCDMA2K|RLCDMA2K:OBWidth:LIMit[:STATe] <boolean>

                 [:SENSe]:FLCDMA2K|RLCDMA2K:OBWidth:LIMit[:STATe]?

**Arguments**   <boolean> ::= {ON|OFF|1|0}  
 ON or 1 enables the limit testing.  
 OFF or 0 disables the limit testing.

**Measurement Modes**   DEMFLCDMA2K, DEMRLCDMA2K

**Examples**   :SENSe:FLCDMA2K:OBWidth:LIMit:STATe ON  
 sets the limit testing to ON for the OBW measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:OBWidth:PERCent (?)

Sets or queries the occupied bandwidth for the OBW measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:OBWidth:PERCent <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:OBWidth:PERCent?

**Arguments** <numeric\_value> ::= <NRF> specifies the occupied bandwidth.  
Range: 80% to 99.99% (default: 99%).

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:OBWidth:PERCent 95PCT  
sets the occupied bandwidth to 95% for the OBW measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:PCCHannel Subgroup

The [:SENSe]:*Standard*:PCCHannel commands set up the conditions related to the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

**Command Tree**

```
[:SENSe]
  :FLCDMA2K|RLCDMA2K
    :PCCHannel
      :ACCThreshold      <numeric_value>
      :FILTter
      :MEASurement       OFF|EQComp|COMP
      :IQSwap             <boolean>
      :LIMit
      :PHASE
        [:STATE]         <boolean>
      :TIME
        [:STATE]         <boolean>
      :PNOFFset           <numeric_value>
      :RConfig            <string>
      :SElect
        :CODE            <numeric_value>
        :PCG             <numeric_value>
      :WCODE              COMPosite|W2L|W4L|W8L|W16L|
                           W32L|W64L|W128L
```

## [:SENSe]:Standard:PCCHannel:ACCThreshold (?)

Sets or queries the active channel threshold level (in dB from the pilot), which is used for deciding whether a code channel is active or inactive, for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:PCCHannel:ACCThreshold <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:PCCHannel:ACCThreshold?

**Arguments** <numeric\_value> ::= <NRF> specifies the active channel threshold level.  
Range: -50 to 50 dB.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:PCCHannel:ACCThreshold -50dB  
sets the active channel threshold level to -50 dB for the pilot to code channel measurement in the cdma2000 forward link analysis.

## [:SENSe]:Standard:PCCHannel:FILTter:MEASurement (?)

Selects or queries the measurement filter for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K:PCCHannel:FILTter:MEASurement {OFF|EQComp|COMP}

[:SENSe]:FLCDMA2K:PCCHannel:FILTter:MEASurement?

**Arguments** OFF specifies that no measurement filter is used.  
EQComp selects the Complementary filter + EQ (equalizer).  
COMP selects the Complementary filter

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:PCCHannel:FILTter:MEASurement COMP  
selects the Complementary filter for the pilot to code channel measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:PCCChannel:IQSswap (?)

Sets or queries whether to enable or disable IQ swapping for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:PCCChannel:IQSswap <bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:PCCChannel:IQSswap?

**Arguments** <bool ean>: :={ON|OFF|1|0}  
ON or 1 enables the IQ swapping.  
OFF or 0 disables the IQ swapping.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:PCCChannel:IQSswap ON  
sets the IQ swapping to ON for the pilot to code channel measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:PCCChannel:LIMit:PHASE[:STATe] (?)

Sets or queries whether to enable or disable the phase limit checking for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:PCCChannel:LIMit:PHASE[:STATe]  
<bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:PCCChannel:LIMit:PHASE[:STATe]?

**Arguments** <bool ean>: :={ON|OFF|1|0}  
ON or 1 enables the phase limit testing.  
OFF or 0 disables the phase limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:PCCChannel:LIMit:PHASE:STATe ON  
enables the phase limit testing for the pilot to code channel measurement in the cdma2000 forward link analysis.

**[:SENSe]:Standard:PCCHannel:LIMit:TIME[:STATe] (?)**

Sets or queries whether to enable or disable the time limit testing for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:PCCHannel:LIMit:TIME[:STATe] <bool ean>

[:SENSe]:FLCDMA2K|RLCDMA2K:PCCHannel:LIMit:TIME[:STATe]?

**Arguments** <bool ean> ::= {ON|OFF|1|0}

ON or 1 enables the time limit testing.

OFF or 0 disables the time limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:PCCHannel:LIMit:TIME:STATe ON  
enables the time limit testing for the pilot to code channel measurement in the cdma2000 forward link analysis.

**[:SENSe]:FLCDMA2K:PCCHannel:PNOffset (?)**

Sets or queries the PN offset for the pilot to code channel measurement in the cdma2000 forward link analysis.

**Syntax** [:SENSe]:FLCDMA2K:PCCHannel:PNOffset <numeric\_value>

[:SENSe]:FLCDMA2K:PCCHannel:PNOffset?

**Arguments** <numeric\_value> ::= <NR1> specifies the PN offset.  
Range: 0 to 511.

**Measurement Modes** DEMFLCDMA2K

**Examples** :SENSe:FLCDMA2K:PCCHannel:PNOffset 100  
sets the PN offset to 100 for the pilot to code channel measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:PCCHannel:RCONfig (?)

Selects or queries the available radio configuration for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:PCCHannel:RCONfig <string>

[:SENSe]:FLCDMA2K|RLCDMA2K:PCCHannel:RCONfig?

**Arguments** <string> ::= {"CDMAONE" | "CDMA2K1X"}  
"CDMAONE" selects RC1/RC2 for FLCDMA2K.  
"CDMA2K1X" selects RC3/RC4/RC5 for FLCDMA2K and RC3/RC4 for RLCDMA2K.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:PCCHannel:RCONfig "CDMAONE"  
sets the radio configuration to RC1/RC2 for the pilot to code channel measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:PCCHannel:SElect:CODE (?)

Sets or queries the code in the PCG for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:PCCHannel:SElect:CODE <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:PCCHannel:SElect:CODE?

**Arguments** <numeric\_value> ::= <NR1> specifies the code in the PCG.  
The available ranges are as follows:

- **FLCDMA2K:**  
64 fixed when the [:SENSe]:*Standard*:PCCHannel:RCONfig command is set to "CDMAONE".  
4 to 128 when the [:SENSe]:*Standard*:PCCHannel:RCONfig command is set to "CDMA2K1X".
- **RLCDMA2K:**  
2 to 64 when the [:SENSe]:*Standard*:PCCHannel:RCONfig command is set to "CDMA2K1X".  
Not supported when the [:SENSe]:*Standard*:PCCHannel:RCONfig command is set to "CDMAONE".

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

---

<b>Examples</b>	:SENSe:FLCDMA2K:PCCHannel:SElect:CODE 1 sets the code in the PCG to 1 for the pilot to code channel measurement in the cdma2000 forward link analysis.
<b>Related Commands</b>	[ :SENSe]:FLCDMA2K RLCDMA2K:PCCHannel:RCONFi g

## [:SENSe]:*Standard*:PCCHannel:SElect:PCG (?)

Sets or queries the PCG (power control group) for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis.

<b>Syntax</b>	[ :SENSe]:FLCDMA2K RLCDMA2K:PCCHannel:SElect:PCG <numerical_value> [ :SENSe]:FLCDMA2K RLCDMA2K:PCCHannel:SElect:PCG?
<b>Arguments</b>	<numerical_value> ::= <NR1> specifies the PCG. Range: -(number of analyzed half slots -1) to 0.
<b>Measurement Modes</b>	DEMFLCDMA2K, DEMRLCDMA2K
<b>Examples</b>	:SENSe:FLCDMA2K:PCCHannel:SElect:PCG -10 sets the PCG to -10 for the pilot to code channel measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:PCCChannel:WCODe (?)

Selects or queries the Walsh code length for the pilot to code channel measurement in the cdma2000 forward link or reverse link analysis. This command is only available when the [:SENSe]:*Standard*:RConfig command is set to CDMA2K1X.

### Syntax

[: SENSe]: FLCDMA2K | RLCDMA2K: PCCHannel : WCODe {COMPosi te|W2L|W4L|W8L  
|W16L|W32L|W64L|W128L}

[: SENSe]: FLCDMA2K | RLCDMA2K: PCCHannel : WCODe?

### Arguments

The arguments and lengths are listed below:

Argument	Length
COMPosi te	composite
W2L <sup>1</sup>	2
W4L	4
W8L	8
W16L	16
W32L	32
W64L	64
W128L <sup>2</sup>	128

- 1 This argument is only available in the RLCDMA2K standard.  
2 This argument is only available in the FLCDMA2K standard.

### Measurement Modes

DEMFLCDMA2K, DEMRLCDMA2K

### Examples

: SENSe: FLCDMA2K: PCCHannel : WCODe W4L

sets the Walsh code length to 4 for the pilot to code channel measurement in the cdma2000 forward link analysis.

### Related Commands

[: SENSe]: FLCDMA2K | RLCDMA2K: PCCHannel : RConfig

## [:SENSe]:RLCDMA2K:PVTIme Subgroup

The [:SENSe]:RLCDMA2K:PVTIme commands set up the conditions related to the gated output power measurement in the cdma2000 forward link analysis. These commands are only available for the cdma2000 reverse link standard.

<b>Command Tree</b>	[:SENSe]	
	:RLCDMA2K	
	:PVTIme	
	:BURSt	
	:GATE	RPCChannel   RFChannel
	:OFFSet	<numerical_value>
	:SYNC	REDGe   MPoint   TPosition
	:LIMit	
	:ZONE[1 2 3 4 5]	
	[:STATe]	<boolean>
	:RCHannel	
	:LEVEL	<numerical_value>
	:MODE	AUTO   MANUAL

## [:SENSe]:RLCDMA2K:PVTIme:BURSt:GATE (?)

Sets or queries the burst gate for the gated output power measurement in the cdma2000 reverse link analysis.

**Syntax**   [:SENSe]:RLCDMA2K:PVTIme:BURSt:GATE {RPCChannel | RFChannel }

                 [:SENSe]:RLCDMA2K:PVTIme:BURSt:GATE?

**Arguments**   RPCChannel sets the reverse pilot channel or RC1/RC2.  
RFChannel sets the reverse fundamental channel.

**Measurement Modes** DEMRLCDMA2K

**Examples**   :SENSe:RLCDMA2K:PVTIme:BURSt:GATE RFChannel  
sets the burst gate to the reverse fundamental channel for the gated output power measurement in the cdma2000 reverse link analysis.

## [:SENSe]:RLCDMA2K:PVTIme:BURSt:OFFSet (?)

Sets or queries the burst offset between the trigger position and burst position for the gated output power measurement in the cdma2000 reverse link analysis. This command is only available when the [:SENSe]:RLCDMA2K:PVTIme:BURSt:SYNC command is set to TPOSition.

**Syntax** [:SENSe]:RLCDMA2K:PVTIme:BURSt:OFFSet <numer ic\_val ue>

[:SENSe]:RLCDMA2K:PVTIme:BURSt:OFFSet?

**Arguments** <numer ic\_val ue> ::=<NRF> specifies the burst offset.  
Range: -1 E-3 to 1 E-3 [s].

**Measurement Modes** DEMRLCDMA2K

**Examples** :SENSe:RLCDMA2K:PVTIme:BURSt:OFFSet 100us  
sets the burst offset to 100 µs for the gated output power measurement in the cdma2000 reverse link analysis.

**Related Commands** [:SENSe]:RLCDMA2K:PVTIme:BURSt:SYNC

## [:SENSe]:RLCDMA2K:PVTIme:BURSt:SYNC (?)

Sets or queries the burst sync for the gated output power measurement in the cdma2000 reverse link analysis.

**Syntax** [:SENSe]:RLCDMA2K:PVTIme:BURSt:SYNC {REDGe|MPOi nt|TPOSi ti on}

[:SENSe]:RLCDMA2K:PVTIme:BURSt:SYNC?

**Arguments** REDGe specifies the rising edge.  
MPOi nt specifies the middle point.  
TPOSi ti on specifies the trigger position.

**Measurement Modes** DEMRLCDMA2K

**Examples** :SENSe:RLCDMA2K:PVTIme:BURSt:SYNC TPOSi ti on  
sets the burst sync to the trigger position for the gated output power measurement in the cdma2000 reverse link analysis.

**[:SENSe]:RLCDMA2K:PVTime:LIMit:ZONE[1|2|3|4|5[:STATe] (?)**

Sets or queries whether to enable or disable the zone limit testing for the gated output power measurement in the cdma2000 reverse link analysis.

**Syntax** [:SENSe]:RLCDMA2K:PVTime:LIMit:ZONE[1|2|3|4|5[:STATe] <boolean>

[:SENSe]:RLCDMA2K:PVTime:LIMit:ZONE[1|2|3|4|5[:STATe]?

Zones 1, 2, 3, 4, and 5 correspond to Zones A, B, C, D, and E in the limit editor, respectively.

**Arguments** <boolean> ::= {ON|OFF|1|0}

ON or 1 enables the zone limit testing.

OFF or 0 disables the zone limit testing.

**Measurement Modes** DEMRLCDMA2K

**Examples** :SENSe:RLCDMA2K:PVTime:LIMit:ZONE1 ON

enables the limit testing of the zone 1 for the gated output power measurement in the cdma2000 reverse link analysis.

**[:SENSe]:RLCDMA2K:PVTime:RCHannel:LEVel (?)**

Sets or queries the reference channel level to measure the power level in dB. This command is only available when the [:SENSe]:RLCDMA2K:PVTime:RCHannel:MODE command is set to MANual.

**Syntax** [:SENSe]:RLCDMA2K:PVTime:RCHannel:LEVel <numeric\_value>

[:SENSe]:RLCDMA2K:PVTime:RCHannel:LEVel ?

**Arguments** <numeric\_value> ::= <NRf> specifies the reference channel level.  
Range: -150 to 30 dBm.

**Measurement Modes** DEMRLCDMA2K

**Examples** :SENSe:RLCDMA2K:PVTime:RCHannel:LEVel -10dBm

sets the reference channel level to -10 dBm for the gated output power measurement in the cdma2000 reverse link analysis.

**Related Commands** [:SENSe]:RLCDMA2K:PVTime:RCHannel:MODE

## [:SENSe]:RLCDMA2K:PVTIme:RCHannel:MODE (?)

Sets or queries the mode of the reference channel level to measure the power level in dB.

**Syntax** [:SENSe]:RLCDMA2K:PVTIme:RCHannel:MODE {AUTO|MANual}

[:SENSe]:RLCDMA2K:PVTIme:RCHannel:MODE?

**Arguments**  
AUTO the reference level is measured from the input signal.  
MANual the reference level can be defined by the [:SENSe]:RLCDMA2K:PVTIme:RCHannel:LEVel command.

**Measurement Modes** DEMRLCDMA2K

**Examples** :SENSe:RLCDMA2K:PVTIme:RCHannel:MODE AUTO  
sets the mode of the reference channel level to AUTO for the gated output power measurement in the cdma2000 reverse link analysis.

**Related Commands** [:SENSe]:RLCDMA2K:PVTIme:RCHannel:LEVel

## [:SENSe]:*Standard*:SEMask Subgroup

The [:SENSe]:*Standard*:SEMask commands set up the conditions related to the spectrum emission mask measurement in the cdma2000 forward link or reverse link analysis.

### Command Tree

	[:SENSe]	
	:FLCDMA2K RLCDMA2K	
	:SEMask	
	:BANDwidth BWIDth	
	:INtegration	<numeric_value>
	:BURSt	
	:OFFSet	<numeric_value>
	:SYNC	REDGe MPOint TP0Sition
	:FILTer	
	:COEFFicient	<numeric_value>
	:TYPE	RECTangle GAUSSian NYquist RNYquist
	:LIMit	
	:ISPurious	
	:ZONE[1] 2 3 4 5	
	[:STATE]	<boolean>
	:OFCHannel	
	:ZONE[1] 2 3 4 5	
	[:STATE]	<boolean>
	:MEASurement	OFCHannel ISPurious
	:RChannel	
	:LEVel	<numeric_value>
	:MODE	AUTO MANual
	:SLOT	
	:GATE	<numeric_value>

## [:SENSe]:*Standard*:SEMask:BANDwidth|BWIDth:INTegration (?)

Sets or queries the channel bandwidth for the spectrum emission mask measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:BANDwidth|BWIDth:INTegration <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:BANDwidth|BWIDth:INTegration?

**Arguments** <numeric\_value> ::= <NRF> specifies the channel bandwidth.  
Range: Span/20 to full span [Hz].

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:BANDwidth:INTegration 2.5MHz  
sets the channel bandwidth to 2.5 MHz for the spectrum emission mask measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:SEMask:BURSt:OFFSet (?)

Sets or queries the burst offset between the trigger position and burst position for the spectrum emission mask measurement in the cdma2000 forward link analysis. This command is only available when the [:SENSe]:*Standard*:SEMask:BURSt:SYNC command is set to TPOSIon.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:BURSt:OFFSet <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:BURSt:OFFSet?

**Arguments** <numeric\_value> ::= <NRF> specifies the burst offset.  
Range: -1 E-3 to 1 E-3 [s].

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:BURSt:OFFSet 100us  
sets the burst offset to 100  $\mu$ s for the spectrum emission mask measurement in the cdma2000 forward link analysis.

**Related Commands** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:BURSt:SYNC

## [:SENSe]:Standard:SEMask:BURSt:SYNC (?)

Sets or queries the burst sync for the spectrum emission mask measurement in the cdma2000 forward link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:BURSt:SYNC  
{REDGe|MPOi nt|TPOSi ti on}

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:BURSt:SYNC?

**Arguments**  
REDGe specifies the rising edge.  
MPOi nt specifies the middle point.  
TPOSi ti on specifies the trigger position.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** [:SENSe]:FLCDMA2K:SEMask:BURSt:SYNC TPOSi ti on  
sets the burst sync to the trigger position for the spectrum emission mask measurement in the cdma2000 forward link analysis.

## [:SENSe]:Standard:SEMask:FILTer:COEFFicient (?)

Sets or queries the filter roll-off rate for the spectrum emission mask measurement in the cdma2000 forward link or reverse link analysis. This command is only available when the [:SENSe]:Standard:SEMask:FILTer:TYPE command is set to NYQuist or RNYQuist.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:FILTer:COEFFicient  
<numer i c\_val ue>

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:FILTer:COEFFicient?

**Arguments** <numer i c\_val ue>:=<NRf> specifies the roll-off rate.  
Range: 0.0001 to 1 (default: 0.5).

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** [:SENSe]:FLCDMA2K:SEMask:FILTer:COEFFicient 0.1  
sets the filter roll-off rate to 0.1 for the spectrum emission mask measurement in the cdma2000 forward link analysis.

**Related Commands** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:FILTer:TYPE

**[:SENSe]:*Standard*:SEMask:FILTter:TYPE (?)**

Selects or queries the filter for the spectrum emission mask measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:FILTter:TYPE {RECTangle  
|GAUSSian|NYQuist|RNYQuist}

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:FILTter:TYPE?

**Arguments** The arguments and filters are listed below:

Argument	Filter
RECTangle	Rectangular
GAUSSian	Gaussian
NYQuist	Nyquist
RNYQuist	Root Nyquist

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:FILTter:TYPE NYQuist  
selects the Nyquist filter for the spectrum emission measurement in the cdma2000 forward link analysis.

**[:SENSe]:*Standard*:SEMask:LIMit:ISPurious:ZONE[1|2|3|4|5[:STATe] (?)**

Sets or queries whether to enable or disable the inband spurious zone limit testing for the spectrum emission mask measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:LIMit:ISPurious:ZONE[1|2|3|4|5[:STATe] <boolean>

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:LIMit:ISPurious:ZONE[1|2|3|4|5[:STATe]?

Zones 1, 2, 3, 4, and 5 correspond to Zones A, B, C, D, and E in the limit editor, respectively.

**Arguments** <boolean>: :={ON|OFF|1|0}  
ON or 1 enables the inband spurious zone limit testing.  
OFF or 0 disables the inband spurious zone limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:LIMit:ISPurious:ZONE1:STATe ON  
enables the inband spurious limit testing of the zone 1 for the spectrum emission mask measurement in the cdma2000 forward link analysis.

### [:SENSe]:Standard:SEMask:LIMit::OFCHannel:ZONE[1|2|3|4|5[:STATe] (?)

Sets or queries whether to enable or disable the offset from the channel zone limit testing for the spectrum emission mask measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:LIMit:OFCHannel:ZONE[1|2|3|4|5[:STATe]<boolean>

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:LIMit:OFCHannel:ZONE[1|2|3|4|5[:STATe]?

Zones 1, 2, 3, 4, and 5 correspond to Zones A, B, C, D, and E in the limit editor, respectively.

**Arguments** <boolean> ::= {ON|OFF|1|0}

ON or 1 enables the offset from the channel zone limit testing.

OFF or 0 disables the offset from the channel zone limit testing.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:LIMit:OFCHannel:ZONE1:STATe ON

enables the offset from the channel limit testing of the zone 1 for the spectrum emission mask measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:SEMask:MEASurement (?)

Sets or queries the limit table type used for limit testing for the spectrum emission mask measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:MEASurement  
{OFCHannel | ISPuri ous}

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:MEASurement?

**Arguments**  
OFCHannel selects the Offset From Channel type where frequency zones are specified by the difference from the center frequency.  
ISPuri ous selects the Inband Spurious type in which frequency zones are specified by the absolute values.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:MEASurement ISPuri ous  
selects the Inband Spurious limit table for the spectrum emission mask measurement in the cdma2000 forward link analysis.

## [:SENSe]:*Standard*:SEMask:RCHannel:LEVel (?)

Sets or queries the reference channel level to measure the spurious emission level in dBc. This command is only available when the [:SENSe]:*Standard*:SEMask:RCHannel:MODE command is set to MANual.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:RCHannel:LEVel <numeric\_value>  
[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:RCHannel:LEVel?

**Arguments** <numeric\_value>::=<NRF> specifies the reference level.  
Range: -150 to 30 dBm.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:RCHannel:LEVel -10dBm  
sets the reference channel level to -10 dBm for the spectrum emission mask measurement in the cdma2000 forward link analysis.

**Related Commands** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:RCHannel:MODE

## [:SENSe]:*Standard*:SEMask:RCHannel:MODE (?)

Sets or queries the mode of the reference channel level to measure the spurious emission level in dBc.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:RCHannel:MODE {AUTO|MANual}

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:RCHannel:MODE?

**Arguments**  
 AUTO the reference level is measured from the input signal.  
 MANual the reference level can be defined by the [:SENSe]:*Standard*:SEMask:RCHannel:LEVel command.

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:RCHannel:MODE AUTO  
 sets the mode of the reference channel level to AUTO for the spectrum emission mask measurement in the cdma2000 forward link analysis.

**Related Commands** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:RCHannel:LEVel

## [:SENSe]:*Standard*:SEMask:SLOT:GATE (?)

Sets or queries the slot gate time for the spectrum emission mask measurement in the cdma2000 forward link or reverse link analysis.

**Syntax** [:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:SLOT:GATE <numeric\_value>

[:SENSe]:FLCDMA2K|RLCDMA2K:SEMask:SLOT:GATE?

**Arguments** <numeric\_value> ::= <NRF> specifies the slot gate time.  
 Range: 180 E-6 to 840 E-6 [s].

**Measurement Modes** DEMFLCDMA2K, DEMRLCDMA2K

**Examples** :SENSe:FLCDMA2K:SEMask:SLOT:GATE 200us  
 sets the slot gate time to 200  $\mu$ s for the spectrum emission mask measurement in the cdma2000 forward link analysis.





# Appendices



# Appendix A: Specifications

Tables A-1 and A-2 list the characteristics of the cdma2000 forward link and reverse link measurements.

All listed specifications are guaranteed unless labeled with typical. Typical specifications are provided for your convenience but are not guaranteed.

Table A-1: cdma2000 forward link

Characteristics	Description
Channel power	
Minimum power at RF input	-50 dBm
Absolute power measurement accuracy (at 20 to 30 °C, excluding mismatch error), typical	±0.6 dB at conditions below: Signal frequency: 824 to 960 MHz or 1750 to 2170 MHz Signal power: 0 dBm to -50 dBm After Auto Level is performed at 10 MHz span.
Relative power measurement accuracy (at 20 to 30 °C, excluding mismatch error), typical	±0.2 dB at conditions below: Signal frequency: 824 to 960 MHz or 1750 to 2170 MHz Signal power: 0 dBm to -30 dBm After Auto Level is performed at 10 MHz span, 0 dBm input.
Resolution	0.01 dB
ACPR	
Minimum carrier power at RF input	-40 dBm
Dynamic range	At -5 dBm signal input
765 kHz offset	76 dB (30 kHz BW)
1.995 MHz offset	81 dB (30 kHz BW)
3.125 MHz offset	81 dB (30 kHz BW)
4 MHz offset	82 dB (30 kHz BW)
CCDF	
Histogram resolution	0.01 dB
Intermodulation distortion	
Measurement filter	Rectangular, Root Nyquist, Nyquist, and Gaussian
Occupied bandwidth	
Minimum carrier power at RF input	-50 dBm
Measurement accuracy	0.2%

## Appendix A: Specifications

---

**Table A-1: cdma2000 forward link (cont.)**

Characteristics	Description
Spectrum emission mask	
Minimum carrier power at RF input	-5 dBm
Dynamic range	
1.995 MHz offset	82 dB (30 kHz BW)
Code domain power	
Relative code domain power accuracy	±0.15 dB ±0.075 dB (typical)
QPSK EVM	
Minimum carrier power at RF input	-40 dBm
EVM floor, typical	2.0%
Modulation Accuracy (composite)	
Minimum carrier power at RF input	-40 dBm
Composite EVM floor, typical	2.0%
Rho	0.999
Frequency error accuracy	±10 Hz + center frequency accuracy
Timing accuracy (tau)	±250 ns

**Table A-2: cdma2000 reverse link**

Characteristics	Description
Channel power	
Minimum power at RF input	-50 dBm
Absolute power measurement accuracy (at 20 to 30 °C, excluding mismatch error), typical	±0.6 dB at conditions below:  Signal frequency: 824 to 960 MHz or 1750 to 2170 MHz Signal power: 0 dBm to -50 dBm After Auto Level is performed at 10 MHz span.
Relative power measurement accuracy (at 20 to 30 °C, excluding mismatch error), typical	±0.2 dB at conditions below:  Signal frequency: 824 to 960 MHz or 1750 to 2170 MHz Signal power: 0 dBm to -30 dBm After Auto Level is performed at 10 MHz span, 0 dBm input.
Resolution	0.01 dB

Table A-2: cdma2000 reverse link (cont.)

Characteristics	Description
ACPR	
Minimum carrier power at RF input	-40 dBm
Dynamic range	At -5 dBm signal input
900 kHz offset	76 dB (30 kHz BW)
1.995 MHz offset	81 dB (30 kHz BW)
3.125 MHz offset	81 dB (30 kHz BW)
4 MHz offset	82 dB (30 kHz BW)
CCDF	
Histogram resolution	0.01 dB
Intermodulation distortion	
Measurement filter	Rectangular, Root Nyquist, Nyquist, and Gaussian
Occupied bandwidth	
Minimum carrier power at RF input	-50 dBm
Measurement accuracy	0.2%
Spectrum emission mask	
Minimum carrier power at RF input	-5 dBm
Dynamic range	
1.995 MHz offset	82 dB (30 kHz BW)
Code domain power	
Relative code domain power accuracy	$\pm 0.15$ dB $\pm 0.075$ dB (typical)
QPSK EVM	
Minimum carrier power at RF input	-40 dBm
EVM floor, typical	2.0%
Modulation Accuracy (composite)	
Minimum carrier power at RF input	-40 dBm
Composite EVM floor, typical	2.0%
Rho	0.999
Frequency error accuracy	$\pm 10$ Hz + center frequency accuracy

## Appendix A: Specifications

# Appendix B: Factory Default Settings

Tables B-1 and B-2 list the factory default settings of the remote commands. These default settings can be set by using the \*RST command.

**NOTE.** Throughout the header descriptions in this section, the word **Standard** in *italics* is substituted for either of the following two measurement standards; *FLCDMA2K* (*cdma2000 forward link*) or *RLCDMA2K* (*cdma2000 reverse link*).

Table B-1: Factory default settings:-DISPlay commands

Header	Default settings
<b>:DISPlay:<i>Standard</i>:CCDF subgroup</b>	
:DISPlay: <i>Standard</i> :CCDF:LINE:GAUSSian[:STATe]	ON
:DISPlay: <i>Standard</i> :CCDF:LINE:REFerence[:STATe]	OFF
:DISPlay: <i>Standard</i> :CCDF:X[:SCALe]:AUTO	ON
:DISPlay: <i>Standard</i> :CCDF:X[:SCALe]:MAXimum	150 dB
:DISPlay: <i>Standard</i> :CCDF:X[:SCALe]:OFFSet	0
:DISPlay: <i>Standard</i> :CCDF:Y[:SCALe]:MAXimum	100%
:DISPlay: <i>Standard</i> :CCDF:Y[:SCALe]:MINimum	10 μ%
<b>:DISPlay:<i>Standard</i>:DDEMod subgroup</b>	
:DISPLay: <i>Standard</i> :DDEMod:SVlew:FORMAT	SPECtrum
:DISPLay: <i>Standard</i> :DDEMod:SVlew:X[:SCALe]:OFFSet	20.5 MHz
:DISPLay: <i>Standard</i> :DDEMod:SVlew:X[:SCALe]:RANGE	5 MHz
:DISPLay: <i>Standard</i> :DDEMod:SVlew:Y[:SCALe]:OFFSet	0
:DISPLay: <i>Standard</i> :DDEMod:SVlew:Y[:SCALe]:RANGE	100 dB
<b>:DISPLay:<i>Standard</i>:SPECtrum subgroup</b>	
:DISPLay: <i>Standard</i> :SPECtrum:X[:SCALe]:OFFSet	1.4925 GHz
:DISPLay: <i>Standard</i> :SPECtrum:X[:SCALe]:PDIvision	1.5 MHz/div
:DISPLay: <i>Standard</i> :SPECtrum:Y[:SCALe]:OFFSet	0
:DISPLay: <i>Standard</i> :SPECtrum:Y[:SCALe]:PDIvision	10 dB/div
<b>:DISPLay:<i>Standard</i>:WAVEform subgroup</b>	
:DISPLay: <i>Standard</i> :WAVEform:X[:SCALe]:OFFSet	-40 μs
:DISPLay: <i>Standard</i> :WAVEform:X[:SCALe]:PDIvision	4 μs/div
:DISPLay: <i>Standard</i> :WAVEform:Y[:SCALe]:OFFSet	-100 dBm
:DISPLay: <i>Standard</i> :WAVEform:Y[:SCALe]:PDIvision	100 dB/div

Table B-2: Factory default settings-:SENSe commands

Header	Default settings
<b>[:SENSe]:Standard subgroup</b>	
[:SENSe]:Standard:ACQuisition:CHIPs	6144
[:SENSe]:Standard:ACQuisition:HISTory	0
[:SENSe]:Standard:ACQuisition:SEConds	4.998 ms
[:SENSe]:Standard:ANALysis:INTerval	6
[:SENSe]:Standard:ANALysis:OFFSet	0
[:SENSe]:Standard:BLOCK	0
[:SENSe]:Standard:MEASurement	0
[:SENSe]:Standard:SPECTrum:OFFSet	OFF
[:SENSe]:Standard:ACQuisition:TINTerval	0
<b>[:SENSe]:Standard:ACPower subgroup</b>	
[:SENSe]:Standard:ACPower:BANDwidth BWIDth:INTegration	1.23 MHz
[:SENSe]:Standard:ACPower:FILTter:TYPE	RECTangle
[:SENSe]:Standard:ACPower:LIMit:ADJacent[1] 2 3.. 12[:STATE]	1 to 5: ON 6 to 12: OFF
<b>[:SENSe]:Standard:CCDF subgroup</b>	
[:SENSe]:Standard:CCDF:THreshold	-150 dBm
<b>[:SENSe]:Standard:CDPower subgroup</b>	
[:SENSe]:Standard:CDPower:ACCThreshold	FLCDMA2K: -27 dB RLCDMA2K: -21 dB
[:SENSe]:Standard:CDPower:FILTter:MEASurement	FLCDMA2K: EOComp RLCDMA2K: COMP
[:SENSe]:Standard:CDPower:IQSswap	OFF
[:SENSe]:Standard:CDPower:MLEvel	SYMBOL0
[:SENSe]:FLCDMA2K:CDPower:PNOFFset	0
[:SENSe]:FLCDMA2K:CDPower:QOF	0
[:SENSe]:Standard:CDPower:SELect:CODE	0
[:SENSe]:Standard:CDPower:SELect:PCG	0
[:SENSe]:Standard:CDPower:WCODE	COMPosite
<b>[:SENSe]:Standard:CHPower subgroup</b>	
[:SENSe]:Standard:CHPower:BANDwidth BWIDth:INTegration	1.23 MHz
[:SENSe]:Standard:CHPower:FILTter:TYPE	RECTangle
[:SENSe]:Standard:CHPower:LIMit[:STATE]	OFF

Table B-2: Factory default settings-:SENSe commands (cont.)

Header	Default settings
<b>[:SENSe]:Standard:IM subgroup</b>	
<b>[:SENSe]:Standard:IM:BANDwidth BWIDth:INTegration</b>	1.23 MHz
<b>[:SENSe]:Standard:IM:FILTter:TYPE</b>	RECTangle
<b>[:SENSe]:Standard:IM:LIMit:FORDER[:STATe]</b>	ON
<b>[:SENSe]:Standard:IM:LIMit:TORDER[:STATe]</b>	ON
<b>[:SENSe]:Standard:IM:SCOFFset</b>	1.25 MHz
<b>[:SENSe]:Standard:MACCuracy subgroup</b>	
<b>[:SENSe]:Standard:MACCuracy:ACCThreshold</b>	FLCDMA2K: -27 dB RLCDMA2K: -21 dB
<b>[:SENSe]:Standard:MACCuracy:FILTter:MEASurement</b>	FLCDMA2K: EQComp RLCDMA2K: COMP
<b>[:SENSe]:Standard:MACCuracy:IQSWap</b>	OFF
<b>[:SENSe]:Standard:MACCuracy:LIMit:EVM:REAK[:STATe]</b>	OFF
<b>[:SENSe]:Standard:MACCuracy:LIMit:EVM:RMS[:STATe]</b>	OFF
<b>[:SENSe]:Standard:MACCuracy:LIMit:PCDerror[:STATe]</b>	OFF
<b>[:SENSe]:Standard:MACCuracy:LIMit:RHO[:STATe]</b>	ON
<b>[:SENSe]:Standard:MACCuracy:LIMit:TAU[:STATe]</b>	ON
<b>[:SENSe]:Standard:MACCuracy:MLEvel</b>	SYMBOL
<b>[:SENSe]:FLCDMA2K:MACCuracy:PNOFFset</b>	0
<b>[:SENSe]:FLCDMA2K:MACCuracy:QOF</b>	0
<b>[:SENSe]:Standard:MACCuracy:SElect:CODE</b>	0
<b>[:SENSe]:Standard:MACCuracy:SElect:PCG</b>	0
<b>[:SENSe]:Standard:MACCuracy:WCODe</b>	COMPOSITE
<b>[:SENSe]:Standard:OBWidth subgroup</b>	
<b>[:SENSe]:Standard:OBWidth:LIMit[:STATe]</b>	ON
<b>[:SENSe]:Standard:OBWidth:PERcent</b>	99%
<b>[:SENSe]:Standard:PCCHannel subgroup</b>	
<b>[:SENSe]:Standard:PCCHannel:ACCThreshold</b>	FLCDMA2K: -27 dB RLCDMA2K: -21 dB
<b>[:SENSe]:Standard:PCCHannel:FILTter:MEASurement</b>	FLCDMA2K: EQComp RLCDMA2K: COMP
<b>[:SENSe]:Standard:PCCHannel:IQSWap</b>	OFF
<b>[:SENSe]:Standard:PCCHannel:LIMit:PHASE[:STATe]</b>	ON
<b>[:SENSe]:Standard:PCCHannel:LIMit:TIME[:STATe]</b>	ON
<b>[:SENSe]:FLCDMA2K:PCCHannel:PNOFFset</b>	0
<b>[:SENSe]:Standard:PCCHannel:SElect:CODE</b>	0
<b>[:SENSe]:Standard:PCCHannel:SElect:PCG</b>	0
<b>[:SENSe]:Standard:PCCHannel:WCODe</b>	COMPOSITE

Table B-2: Factory default settings-:SENSe commands (cont.)

Header	Default settings
<b>[:SENSe]:RLCDMA2K:PVTime subgroup</b>	
[:SENSe]:RLCDMA2K:PVTime:BURSt:OFFSet	416.67 $\mu$ s
[:SENSe]:RLCDMA2K:PVTime:BURSt:SYNC	MPOint
[:SENSe]:RLCDMA2K:PVTime:LIMit:ZONE[1 2 3 4 5[:STATE]	ON
[:SENSe]:RLCDMA2K:PVTime:RCHannel:LEVel	30 dBm
[:SENSe]:RLCDMA2K:PVTime:RCHannel:MODE	AUTO
<b>[:SENSe]:<i>Standard</i>:SEMask subgroup</b>	
[:SENSe]: <i>Standard</i> :SEMask:BANDwidth BWIDth:INTegration	1.2288 MHz
[:SENSe]: <i>Standard</i> :SEMask:BURSt:OFFSet	416.67 $\mu$ s
[:SENSe]: <i>Standard</i> :SEMask:BURSt:SYNC	MPOint
[:SENSe]: <i>Standard</i> :SEMask:FILTer:TYPE	RECTangle
[:SENSe]: <i>Standard</i> :SEMask:LIMit:ISPUrious:ZONE[1 2 3 4 5[:STATE]	OFF
[:SENSe]: <i>Standard</i> :SEMask:LIMit:OFCHannel:ZONE[1 2 3 4 5[:STATE]	OFF
[:SENSe]: <i>Standard</i> :SEMask:MEASurement	OFCHannel
[:SENSe]: <i>Standard</i> :SEMask:RCHannel:LEVel	0
[:SENSe]: <i>Standard</i> :SEMask:RCHannel:MODE	AUTO
[:SENSe]: <i>Standard</i> :SEMask:SLOT:GATE	200 $\mu$ s

# Appendix C: Setting Range

This section lists the setting range of the horizontal and vertical scale for the views.

**Table C-1: Display format and scale**

Display format	Horizontal range	Vertical range
Spectrum	0 Hz to 3 GHz (WCA230A) 0 Hz to 8 GHz (WCA280A)	-200 to 100 dBm
Spectrogram	0 Hz to 3 GHz (WCA230A) 0 Hz to 8 GHz (WCA280A)	-15999 to 0 frame -63999 to 0 frame (Option 02)
Code domain power	Forward link: RC1/RC2: 16 to 64 channels RC3/RC4/RC5: 16 to 128 channels Reverse link: RC3/RC4: 16 to 64 channels	Relative: -200 to 100 dB Absolute: 140 to -160 dBm
Modulation accuracy	fixed	fixed
EVM	Forward link: Chip: 24 to 1536 Symbol: 24 (fixed) Reverse link: Chip: 24 to 1536 Symbol: 24 to 48	-100 to 200%
Amplitude (Mag) error	same as the horizontal range of EVM	-300 to 300%
Phase error	same as the horizontal range of EVM	-675 to 675 degree
Power codogram	same as the horizontal range of Code domain power	-6144 to 0 frame -24579 to 0 frame (Option 02)
Symbol table	max 256	NA
IQ power graph	same as the horizontal range of EVM	-6144 to 0 frame -24579 to 0 frame (Option 02)
Constellation	fixed	fixed



# Appendix D: SCPI Conformance Information

All of the Option 25 commands are based on SCPI Version 1999.0. Tables D-1 through D-6 list all commands supported by the option 25. The columns to the right show whether a command is defined in the SCPI 1999.0 Standard or not.

Table D-1: SCPI conformance information:-CONFigure commands

Command		Defined in SCPI 1999.0	Not Defined in SCPI 1999.0
: CONFi gure : Standard	: ACPower		✓
	: CCDF		✓
	: CDPower		✓
	: CHPower		✓
	: IM		✓
	: MACCuracy		✓
	: OBWi dth		✓
	: PCCHannel		✓
	: PVTi me		✓
	: SEMask		✓

Table D-2: SCPI conformance information:-DISPlay commands

Command		Defined in SCPI 1999.0	Not Defined in SCPI 1999.0
: DISPl ay : Standard	: CCDF : LINE : GAUSSian [: STATE]		✓
	: REFerence [: STATE]		✓
	: STORe		✓
	: X [: SCALE] : AUTO		✓
	: MAXimum		✓
	: OFFSet		✓
	: Y [: SCALE] : FIT		✓
	: FULL		✓
	: MAXimum		✓
	: MINimum		✓

Table D-2: SCPI conformance information:-DISPlay commands (cont.)

Command			Defined in SCPI 1999.0	Not Defined in SCPI 1999.0	
:DDEMod	:MVi ew	:CORDER		✓	
		:FORMAT		✓	
	:X	[{:SCALe}]	:OFFSet	✓	
			:RANGE	✓	
	:Y	[{:SCALe}]	:FIT	✓	
			:FULL	✓	
			:OFFSet	✓	
			:PUNi t	✓	
			:RANGE	✓	
	:SVI ew	:FORMAT		✓	
	:X	[{:SCALe}]	:OFFSet	✓	
			:RANGE	✓	
	:Y	[{:SCALe}]	:FIT	✓	
			:FULL	✓	
			:OFFSet	✓	
			:RANGE	✓	
	:SPECTrum	:X	[{:SCALe}]	:OFFSet	✓
			:PDIVi sion	✓	
	:Y	[{:SCALe}]	:FIT	✓	
			:FULL	✓	
			:OFFSet	✓	
			:PDIVi sion	✓	
	:WAVEform	:X	[{:SCALe}]	:OFFSet	✓
			:PDIVi sion	✓	
	:Y	[{:SCALe}]	:FIT	✓	
			:FULL	✓	
			:OFFSet	✓	
			:PDIVi sion	✓	

Table D-3: SCPI conformance information-:FETCh commands

Command		Defined in SCPI 1999.0	Not Defined in SCPI 1999.0
:FETCh	: Standard : ACPower?		✓
	: CCDF?		✓
	: CDPower?		✓
	: CHPower?		✓
	: IM?		✓
	: MACcuracy?		✓
	: OBWidth?		✓
	: PCChannel ?		✓
	: PVTime?		✓
	: SEMask?		✓
	: DI STribution : CCDF?		✓
	: TAMPlitude : PVTime?		✓
	: SEMask?		✓
	: SPECTrum : ACPower?		✓
	: CHPower?		✓
	: IM?		✓
	: OBWidth?		✓

Table D-4: SCPI conformance information-:MMEMory commands

Command		Defined in SCPI 1999.0	Not Defined in SCPI 1999.0
: MMEMory	: LOAD : LIMit		✓
	: STORe : LIMit		✓
	: STABle		✓

Table D-5: SCPI conformance information:-READ commands

Command		Defined in SCPI 1999.0	Not Defined in SCPI 1999.0
:READ :Standard :ACPower?			✓
:CCDF?			✓
:CHPower?			✓
:IM?			✓
:OBWidth?			✓
:PVTime?			✓
:SEMask?			✓
:DISTribution :CCDF?			✓
:TAMPItude :PVTime?			✓
:SPECTrum :ACPower?			✓
:CHPower?			✓
:IM?			✓
:OBWidth?			✓

Table D-6: SCPI conformance information:-SENSe commands

Command		Defined in SCPI 1999.0	Not Defined in SCPI 1999.0
[:SENSe] :Standard :ACQuisition :CHIPs			✓
:HISTORY			✓
:SEconds			✓
:ANALysis :INTerval			✓
:OFFSET			✓
:BLOCK			✓
[:IMMEDIATE]			✓
:MEASurement			✓
:SPECTrum :OFFSET			✓
:TINTerval			✓
:ACPower :BANDwidth :INTegration  BWIDth			✓
:FILTER :COEFFicient			✓
:TYPE			✓
:LIMIT :ADJacent [1] 2 3.. 12 [:STATe]			✓

Table D-6: SCPI conformance information:-SENSe commands (cont.)

Command			Defined in SCPI 1999.0	Not Defined in SCPI 1999.0
:CCDF	:RMESurement			✓
	:THReShold			✓
:CDPower	:ACCThreshold			✓
	:FILTer	:MEASurement		✓
	:IQSWap			✓
	:MLEvel			✓
	:PNOFFset			✓
	:QOF			
	:SElect	:CODE		✓
		:PCG		✓
	:WCODE			
:CHPower	:BANDwidth	:INTEGRation		✓
	BWIDth			
	:FILTter	:COEFFicient		✓
		:TYPE		✓
	:LIMit	[:STATe]		✓
:IM	:BANDwidth	:INTEGRation		✓
	BWIDth			
	:FILTter	:COEFficient		✓
		:TYPE		✓
	:LIMit	:FORDer	[:STATe]	✓
		:TORDer	[:STATe]	✓
	:SCOFFset			✓
:MACCuracy	:ACCThreshold			✓
	:FILTter	:MEASurement		✓
	:IQSWap			✓
	:LIMit	:EVM	:PEAK [:STATe]	✓
			:RMS [:STATe]	✓
		:PCDerror	[:STATe]	✓
	:MLEvel			✓
	:PNOFFset			✓
	:QOF			
	:RConfig			✓
	:SElect	:CODE		✓
		:PCG		✓
	:WCODE			

Table D-6: SCPI conformance information:-SENSe commands (cont.)

Command			Defined in SCPI 1999.0	Not Defined in SCPI 1999.0
:OBWIdth	:LIMIt [:STATe]			✓
	:PERcent			✓
:PCCHannel	:ACCThreshold			✓
	:FILTer :MEASurement			✓
	:IQSwap			✓
	:LIMIt :PHASE [:STATe]			✓
	:TIME [:STATe]			✓
	:PNOFFset			✓
	:RCONFIG			✓
	:SElect :CODE			✓
	:PCG			✓
	:WCode			
:PVTime	:BURST :GATE			✓
	:OFFSET			✓
	:SYNC			✓
	:LIMIt :ZONE[1] 2 3 [:STATe]  4 5			✓
	:RChannel :LEVel			✓
	:MODE			✓
:SEMask	:BANDwidth  BWIDth	:INTEGRation		✓
	:BURST	:OFFSET		✓
		:SYNC		✓
	:FILTer	:COEFFicient		✓
		:TYPE		✓
	:LIMIt	:ISPurious :ZONE[1] [:STATe]  2 3 4 5		✓
	:OFChannel	:ZONE[1] [:STATe]  2 3 4 5		✓
	:MEASurement			✓
	:RChannel	:LEVel		✓
		:MODE		✓
	:SLOT	:GATE		✓

# Index

## A

ACPR measurement  
forward link, 2-23

## C

CCDF measurement  
forward link, 2-27  
cdma2000 forward link measurements  
ACPR, 2-23  
CCDF, 2-27  
channel power, 2-21  
code domain power, 2-12  
intermodulation, 2-26  
modulation accuracy, 2-4  
occupied bandwidth, 2-22  
pilot to code channel, 2-30  
spectrum emission mask, 2-24  
cdma2000 reverse link measurements, 2-33  
code domain power, 2-42  
gated output power, 2-49  
modulation accuracy, 2-34  
pilot to code channel, 2-45  
Channel power measurement  
forward link, 2-21  
Code domain power display, 2-15  
Code domain power measurement  
forward link, 2-12, 2-42  
Command groups, 3-1  
:CONFigure commands, 3-11  
:CONFigure:Standard:ACPower, 3-11  
:CONFigure:Standard:CCDF, 3-12  
:CONFigure:Standard:CDPower, 3-12  
:CONFigure:Standard:CHPower, 3-13  
:CONFigure:Standard:IM, 3-13  
:CONFigure:Standard:MACCuracy, 3-14  
:CONFigure:Standard:OBWidth, 3-14  
:CONFigure:Standard:PCCChannel, 3-15  
:CONFigure:Standard:PVTime, 3-15  
:CONFigure:Standard:SEMask, 3-16  
Contacting Tektronix, viii

## D

:DISPlay commands, 3-17  
:DISPlay:RLCDMA2K:WAveform:X[:SCALe]:OFF-  
Set(?), 3-38  
:DISPlay:RLCDMA2K:WAveform:X[:SCALe]:PDI-  
Vision(?), 3-39  
:DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:FIT,  
3-39  
:DISPlay:RLCDMA2K:WAve-

form:Y[:SCALe]:FULL, 3-40  
:DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:OFF-  
Set(?), 3-40  
:DISPlay:RLCDMA2K:WAveform:Y[:SCALe]:PDI-  
Vision(?), 3-41  
:DISPlay:Standard:CCDF:LINE:GAUSSian[:STATe],  
3-18  
:DISPlay:Standard:CCDF:LINE:REFer-  
ence[:STATe], 3-19  
:DISPlay:Standard:CCDF:LINE:REFerence:STORe,  
3-19  
:DISPlay:Standard:CCDF:Y[:SCALe]:FULL, 3-21  
:DISPlay:Standard:CCDF:X[:SCALe]:AUTO(?), 3-20  
:DISPlay:Standard:CCDF:X[:SCALe]:MAXimum(?),  
3-20  
:DISPlay:Standard:CCDF:X[:SCALe]:OFFSet(?),  
3-21  
:DISPlay:Standard:CCDF:Y[:SCALe]:FIT, 3-21  
:DISPlay:Standard:CCDF:Y[:SCALe]:FULL, 3-22  
:DISPlay:Standard:CCDF:Y[:SCALe]:MAXimum,  
3-22  
:DISPlay:Standard:CCDF:Y[:SCALe]:MINimum,  
3-23  
:DISPlay:Standard:DDEMod:MVlew:CORDer(?),  
3-25  
:DISPlay:Standard:DDEMod:MVlew:FORMat(?),  
3-26  
:DISPlay:Standard:DDE-  
Mod:MVlew:X[:SCALe]:OFFSet(?), 3-27  
:DISPlay:Standard:DDE-  
Mod:MVlew:X[:SCALe]:RANGE(?), 3-27  
:DISPlay:Standard:DDE-  
Mod:MVlew:Y[:SCALe]:FIT, 3-28  
:DISPlay:Standard:DDE-  
Mod:MVlew:Y[:SCALe]:FULL, 3-28  
:DISPlay:Standard:DDE-  
Mod:MVlew:Y[:SCALe]:OFFSet(?), 3-29  
:DISPlay:Standard:DDEMod:MVlew:Y[:SCALe]:PU-  
Nit(?), 3-29  
:DISPlay:Standard:DDE-  
Mod:MVlew:Y[:SCALe]:RANGE(?), 3-30  
:DISPlay:Standard:DDEMod:SVlew:FORMat(?),  
3-30  
:DISPlay:Standard:DDE-  
Mod:SVlew:X[:SCALe]:OFFSet(?), 3-31  
:DISPlay:Standard:DDE-  
Mod:SVlew:X[:SCALe]:RANGE(?), 3-32  
:DISPlay:Standard:DDEMod:SVlew:Y[:SCALe]:FIT,  
3-32  
:DISPlay:Standard:DDE-  
Mod:SVlew:Y[:SCALe]:FULL, 3-33  
:DISPlay:Standard:DDE-  
Mod:SVlew:Y[:SCALe]:OFFSet(?), 3-33  
:DISPlay:Standard:DDE-  
Mod:SVlew:Y[:SCALe]:RANGE(?), 3-34  
:DISPlay:Standard:SPECtrum:X[:SCALe]:OFFSet(?),  
3-35

:DISPlay:Standard:SPECtrum:X[:SCALE]:PDIVision(?), 3-35  
:DISPlay:Standard:SPECtrum:Y[:SCALE]:FIT, 3-36  
:DISPlay:Standard[SPECtrum:Y[:SCALE]:FULL, 3-36  
:DISPlay:Standard:SPECtrum:Y[:SCALE]:OFFSet(?), 3-36  
:DISPlay:Standard:SPECtrum:Y[:SCALE]:PDIVision(?), 3-37

## E

Editing the measurement limits, 2-51  
EVM display, 2-8

## F

Factory default settings, B-1  
:FETCh commands, 3-43  
:FETCh:RLCDMA2K:PVTIme?, 3-55  
:FETCh:RLCDMA2K:TAMPlitude:PVTIme?, 3-56  
:FETCh:Standard:ACPower?, 3-44  
:FETCh:Standard:CCDF?, 3-45  
:FETCh:Standard:CDPower?, 3-46  
:FETCh:Standard:CHPower?, 3-48  
:FETCh:Standard:DISTRIBUTION:CCDF?, 3-56  
:FETCh:Standard:IM?, 3-48  
:FETCh:Standard:MACAccuracy?, 3-50  
:FETCh:Standard:OBWidth, 3-53  
:FETCh:Standard:PCCHannel?, 3-54  
:FETCh:Standard:SEMask?, 3-55  
:FETCh:Standard:SPECtrum:ACPower?, 3-57  
:FETCh:Standard:SPECtrum:CHPower?, 3-58  
:FETCh:Standard:SPECtrum:IM?, 3-58  
:FETCh:Standard:SPECtrum:OBWidth?, 3-59

## G

Gated output power measurement  
reverse link, 2-49

## I

Intermodulation measurement  
forward link, 2-26  
IQ power graph display, 2-19

## L

Loading measurement limits, 2-60

## M

Magnitude error display, 2-9, 2-39  
MEAS SETUP menu  
  ACPR, 2-23  
  CCDF, 2-28  
  channel power, 2-21  
  code domain power, 2-13, 2-44  
  gated output power, 2-50  
  intermodulation, 2-26  
  modulation accuracy, 2-5  
  occupied bandwidth, 2-22  
  pilot to code channel, 2-31, 2-47  
  spectrum emission mask, 2-24  
Measurement limits editor, 2-51  
:MMEMory commands, 3-61  
:MMEMory:LOAD:LIMit, 3-61  
:MMEMory:STORe:LIMit, 3-62  
:MMEMory:STORe:STABle, 3-62  
Modulation accuracy display, 2-7  
Modulation accuracy measurement  
  forward link, 2-4  
  reverse link, 2-34

## O

OBW measurement  
forward link, 2-22

## P

Phase error display, 2-10, 2-40  
Pilot to code channel measurement  
  forward link, 2-30  
  reverse link, 2-45  
Power codogram display, 2-17  
Product description, 1-1

## R

:READ commands, 3-63  
:READ:RLCDMA2K:PVTIme?, 3-68  
:READ:RLCDMA2K:TAMPlitude:PVTIme?, 3-70  
:READ:Standard:ACPower?, 3-64  
:READ:Standard:CCDF?, 3-65  
:READ:Standard:CHPower?, 3-66  
:READ:Standard:DISTRIBUTION:CCDF, 3-69  
:READ:Standard:IM?, 3-66  
:READ:Standard:OBWidth?, 3-67  
:READ:Standard:SEMask?, 3-68  
:READ:Standard:SPECtrum:ACPower?, 3-70  
:READ:Standard:SPECtrum:CHPower?, 3-71  
:READ:Standard:SPECtrum:IM?, 3-72  
:READ:Standard:SPECtrum:OBWidth?, 3-72  
Related manuals, vii

**S**

Saving measurement limits, 2-60  
 SCPI conformance information, D-1  
 :SENSe Commands, 3-75  
 [:SENSe]:FL1XEVDO:PVTIme:SLOT[:TYPE](?), 3-121  
 [:SENSe]:FLCDMA2K:CDPower:PNOFFset(?), 3-88  
 [:SENSe]:FLCDMA2K:CDPower:QOF(?), 3-89  
 [:SENSe]:FLCDMA2K:MACCuracy:LIM-  
     it:TAU[:STATe](?), 3-103  
 [:SENSe]:FLCDMA2K:MACCuracy:PNOFFset(?), 3-104  
 [:SENSe]:FLCDMA2K:MACCuracy:QOF(?), 3-105  
 [:SENSe]:FLCDMA2K:PCCHannel:PNOFFset(?), 3-113  
 [:SENSe]:RL1XEVDO:PCCHannel:LCMask:I(?), 3-112  
 [:SENSe]:RLCDMA2K:PVTIme:BURSt:GATE(?), 3-117  
 [:SENSe]:RLCDMA2K:PVTIme:BURSt:OFFSET, 3-118  
 [:SENSe]:RLCDMA2K:PVTIme:BURSt:SYNC(?), 3-118  
 [:SENSe]:RLCDMA2K:PVTIme:LIM-  
     it:ZONE[1]2|3|4|5[:STATe](?), 3-119  
 [:SENSe]:RLCDMA2K:PVTIme:RCHannel:LEV-  
     el(?), 3-119  
 [:SENSe]:RLCDMA2K:PVTIme:RCHan-  
     nel:MODE(?), 3-120  
 [:SENSe]:Standard:ACPower:BAND-  
     width|BWIDth:INTegration(?), 3-82  
 [:SENSe]:Standard:ACPower:FILTer:COEFFfi-  
     cient(?), 3-83  
 [:SENSe]:Standard:ACPower:FILTer:TYPE(?), 3-83  
 [:SENSe]:Standard:ACPower:LIMIt:ADJa-  
     cent[1]2|3..12[:STATe](?), 3-84  
 [:SENSe]:Standard:ACPower:LIMIt:UADJa-  
     cent[1]2|3(?), 3-84  
 [:SENSe]:Standard:ACQuisition:CHIPs(?), 3-76  
 [:SENSe]:Standard:ACQuisition:HISTory(?), 3-77  
 [:SENSe]:Standard:ACQuisition:SEConds(?), 3-77  
 [:SENSe]:Standard:ANALysis:INTerval(?), 3-78  
 [:SENSe]:Standard:ANALysis:OFFSet(?), 3-78  
 [:SENSe]:Standard:IM:BANDwidth|BWIDth:INTe-  
     gration(?), 3-95  
 [:SENSe]:Standard:BLOCk(?), 3-79  
 [:SENSe]:Standard:CCDF:RMEasurement, 3-85  
 [:SENSe]:Standard:CCDF:THreshold(?), 3-85  
 [:SENSe]:Standard:CDPower:ACCThreshold(?), 3-86  
 [:SENSe]:Standard:CDPower:FILTer:MEASure-  
     ment(?), 3-87  
 [:SENSe]:Standard:CDPower:IQSswap(?), 3-87  
 [:SENSe]:Standard:CDPower:MLEvel(?), 3-88  
 [:SENSe]:Standard:CDPower:RConfig(?), 3-89  
 [:SENSe]:Standard:CDPower:SElect:CODE(?), 3-90  
 [:SENSe]:Standard:CDPower:SElect:PCG(?), 3-91  
 [:SENSe]:Standard:CDPower:WCODE(?), 3-91  
 [:SENSe]:Standard:CHPower:BAND-  
     width|BWIDth:INTegration(?), 3-92

[:SENSe]:Standard:CHPower:FILTer:COEFFfi-  
     cient(?), 3-93  
 [:SENSe]:Standard:CHPower:FILTer:TYPE(?), 3-94  
 [:SENSe]:Standard:CHPower:LIMIt[:STATe](?), 3-94  
 [:SENSe]:Standard:IM:FILTer:COEFFicient(?), 3-96  
 [:SENSe]:Standard:IM:FILTer:TYPE(?), 3-96  
 [:SENSe]:Standard:IM:LIMIt:FORDer[:STATe](?), 3-97  
 [:SENSe]:Standard:IM:LIMIt:TORDer[:STATe](?), 3-98  
 [:SENSe]:Standard:IM:SCOFFset(?), 3-98  
 [:SENSe]:Standard[:IMMEDIATE], 3-79  
 [:SENSe]:Standard:MACCuracy:ACCThreshold(?), 3-100  
 [:SENSe]:Standard:MACCuracy:FILTer:MEASure-  
     ment(?), 3-100  
 [:SENSe]:Standard:MACCuracy:IQSswap(?), 3-101  
 [:SENSe]:Standard:MACCuracy:LIMIt:EVM:PE-  
     VM[:STATe](?), 3-101  
 [:SENSe]:Standard:MACCuracy:LIM-  
     it:EVM:RMS[:STATe](?), 3-102  
 [:SENSe]:Standard:MACCuracy:LIMIt:PCDer-  
     ror[:STATe](?), 3-102  
 [:SENSe]:Standard:MACCuracy:LIM-  
     it:RHO[:STATe](?), 3-103  
 [:SENSe]:Standard:MACCuracy:MLEvel(?), 3-104  
 [:SENSe]:Standard:MACCuracy:RConfig(?), 3-105  
 [:SENSe]:Standard:MACCuracy:SElect:CODE(?), 3-106  
 [:SENSe]:Standard:MACCuracy:SElect:PCG(?), 3-107  
 [:SENSe]:Standard:MACCuracy:WCODE(?), 3-108  
 [:SENSe]:Standard:MEASurement(?), 3-80  
 [:SENSe]:Standard:OBWidth:LIMIt[:STATe](?), 3-109  
 [:SENSe]:Standard:OBWidth:PERCent(?), 3-110  
 [:SENSe]:Standard:PCCHannel:ACCThreshold(?), 3-111  
 [:SENSe]:Standard:PCCHannel:FILTer:MEASure-  
     ment(?), 3-111  
 [:SENSe]:Standard:PCCHannel:IQSswap(?), 3-112  
 [:SENSe]:Standard:PCCHannel:LIM-  
     it:PHASE[:STATe](?), 3-112  
 [:SENSe]:Standard:PCCHannel:LIM-  
     it:TIME[:STATe](?), 3-113  
 [:SENSe]:Standard:PCCHannel:SElect:CODE(?), 3-114  
 [:SENSe]:Standard:PCCHannel:SElect  
     PCG(?), 3-115  
 [:SENSe]:Standard:PCCHannel:WCODE(?), 3-116  
 [:SENSe]:Standard:SEMask:BANDwidth|BWIDth:IN-  
     TEGRATION, 3-122  
 [:SENSe]:Standard:SEMask:BURSt:OFFSET(?), 3-122  
 [:SENSe]:Standard:SEMask:BURSt:SYNC(?), 3-123  
 [:SENSe]:Standard:SEMask:FILTer:COEFFicient(?), 3-123  
 [:SENSe]:Standard:SEMask:FILTer:TYPE(?), 3-124  
 [:SENSe]:Standard:SEMask:LIMIt:ISPuri-  
     ous:ZONE[1]2|3|4|5[:STATe](?), 3-124  
 [:SENSe]:Standard:SEMask:LIMIt:OFCHan-  
     nel:ZONE[1]2|3|4|5[:STATe](?), 3-125

[:SENSe]:Standard:SEMask:MEASurement(?), 3-126  
[:SENSe]:Standard:SEMask:RCHannel:LEVel(?),  
    3-126  
[:SENSe]:Standard:SEMask:RCHannel:MODE(?),  
    3-127  
[:SENSe]:Standard:SEMask:SLOT:GATE(?), 3-127  
[:SENSe]:Standard:SPECtrum:OFFSet(?), 3-81  
[:SENSe]:Standard:SPECtrum:TINTerval, 3-81  
Setting a measurement limit, 2-53  
Setting measurement limits  
    gated output power, 2-58  
    spectrum emission mask, 2-54, 2-56  
Setting the ACPR limits, 2-54  
Setting the gated output power limits, 2-58  
Setting the spectrum emission mask limits, 2-56  
Specifications, A-1  
Spectrum emission mask measurement  
    forward link, 2-24  
Symbol table display, 2-11

## **U**

Using the measurement limits editor, 2-51