

3444 Triplet Roll Chart Supplement

(To Roll Chart 84-95-061569)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
00A	5.0	8.5	1450-0-2000	6	1	.43/.66	F
01A	5.0	6	1450-0-2000	6	1	.47/.73	F
0Y4	0	33	0090-4-0210	4	8	Rect.	F (1)
		14				Rect.	F (2)
1A4	2.0	7	1460-0-2000	6	1	.47/.73	F (7)
1A5	1.4	7	0146-5-0200	6	1	.55/.85	F
1AB5	1.4	30	1460-0-5220	5	2	.89/1.4	F
1AC5	1.4	0	0501-2-0460	9	1	.39/.60	F
1ADS	1.4	6	0501-2-0460	9	1	.28/.43	F
1AE5	1.25	5	4515-6-2000	9	1	.25/.50	F
1A6	2.0	20	1445-6-2000	8	1	.40/.80	F (7)
1B1	2.35	0	1000-0-3000	11	8	*	
Switch SHORTS-LEAKAGE switch to H-K position							
* Good tube indicates to full scale.							
1BC2	1.25	5	1000-2-0000	4	8	Rect.	(4)F
1BG2	1.4	8	1000-0-0020	4	8	Rect.	F (6)
Insert Filament Leads in 1 and 8 of 8-pin subminiature socket.							
1BH2	1.25	4	1000-0-0020	4	8	Rect.	(4)
1B4P	2.0	29	1460-0-2000	8	1	.34/.52	F (7)
1B5	2.0	20	1400-5-2000	5	1	.37/.57	F (1)
		0	1049-0-2000	11	8	Diode	F (1)(2)
1C5	1.4	10	0146-5-0200	6	2	.95/1.5	F
1C6	2.0	20	1445-6-2000	8	2	.45/.90	F (7)
1C7	2.0	20	0146-5-4200	8	2	.45/.90	F (7)
1C21		0	0300-4-0550	2	7	* Thyatron	
* Reject at 15 on Rect. Scale							
1D5	2.0	9	0146-0-0200	8	1	.46/.71	F (7)
1D7	2.0	20	0146-5-4200	8	2	.40/.80	F (7)
1D8	1.4	12	0146-5-0290	6	2	.65/1.0	F (1)
			0100-0-4290	5	1	.40/.61	F (1)(7)
		0		11	8	Diode	F (2)
1E3	1.25	30	5012-1-0040	5	3	2.3/3.5	F
1E4	1.4	5	0140-5-0200	6	1	.55/.85	F
1E7	2.0	10	029X-5-4160	5	2	.90/1.4	F (1)(2)
This set up to be used on tester above serial #5000							
1E7*	2.0	50	029X-5-4160	5	2	.90/1.4	F (1)(2)
* This set up must be used on tester below serial #5000							
1E8	1.25	13	0501-2-4650	9	1	.20/.40	F
1F4	2.0	6	1450-6-2000	5	2	.91/1.4	F
1F5	2.0	8	0146-5-0200	5	2	.91/1.4	F

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
1F6	2.0	9	1460-0-2000	3	1	.42/.65	F (7)
	-	0	1004-9-2000	11	8	Diode	F (1)(2)
1F7	2.0	8	0140-0-6200	3	1	.42/.65	F (7)
	-	0	0104-9-0200	11	8	Diode	F (1)(2)
1G4	1.4	8	0140-5-0200	6	1	.54/.83	F
1G5	2.0	10	0146-5-0200	6	2	.98/1.5	F
1G8	1.4	10	0145-X-9200	5	1	.44/.68	F (1)(2)
1H4	2.0	7	0140-5-0200	6	1	.55/.85	F
1H6	2.0	22	0140-0-5200	5	1	.37/.57	F
	-	0	0104-9-0200	11	8	Diode	F (1)(2)
1J5	2.0	12	0146-5-0200	6	2	.61/.94	F
1J8	2.0	0	0145-X-9200	5	2	.85/1.3	F (1)(2)
1LA4	1.4	8	1460-0-5020	6	1	.55/.85	F
1LC5	1.4	12	1467-2-5020	8	1	.43/.66	F
1LC6	1.4	50	1445-6-5020	8	1	.30/.60	F
1LD5	1.4	10	1469-0-5020	8	1	.35/.54	F (1)
	-	0	- - -	11	8	Diode	F (2)
1LE3	1.4	20	1400-0-5020	5	2	.84/1.3	F
1LF3	1.4	20	1400-0-5020	5	2	.84/1.3	F
1LG5	1.4	31	1467-2-5020	5	2	.75/1.2	F
1N2	1.25	3	0100-0-0200	4	8	Rect.	F (6)
1N6	1.4	9	0146-5-9200	6	1	.52/.80	F (1)
	-	0	- - -	11	8	Diode	F (2)
1P5	1.4	15	0146-0-0200	5	1	.49/.75	F (7)
1Q5	1.4	7	0146-5-0200	6	2	1.4/2.2	F
1SA6	1.4	31	0175-0-6240	5	2	.62/.95	F
1TS	1.4	8	0146-5-0200	6	2	.76/1.2	F
1TB	1.4	41	4051-2-9060	5	1	.39/.60	F (1)
	-	0	- - -	11	8	Diode	F (2)
1V	6.3	14	2430-0-1000	6	8	Rect.	
1V5	1.4	11	0501-2-0460	6	1	.45/.69	F
2A3	2.8	40	1450-0-2000	2	3	2.6/5.2	F
2A5	2.8	16	1465-3-2000	2	2	1.1/2.2	
2A6	2.8	20	1400-3-2000	1	2	.72/1.1	(1)(7)
	-	0	1049-3-2000	11	8	Diode	(1)(2)
2A7	2.35	50	1464-5-3200	5	2	.80/1.6	(7)
2AF4	2.35	30	4512-3-5400	5	3	5.5/8.5	
2AS2	2.8	3	1000-0-0002	4	8	Rect.	F (6)
Adapter CK							
2B6	2.35	30	1400-5-3200	1	3	1.5/3.0	
	-	30	1045-3-3200	1	2	.90/1.8	
2B7	2.8	27	1460-0-3200	5	2	.62/.95	(1)(7)
	-	0	1004-9-3200	11	8	Diode	(1)(2)
2C36	6.3	12	0254-1-0000	2	3	2.2/4.5	F
Adapter CG or Leads							
2C39	6.3	4	0254-1-0000	1	4	11./22.	F
Adapter Leads							
2-01C	5.0	0	1200-0-0000	11	8	Diode	F (6)
Adapter CG or Leads							

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
2CN3A	2.0	7	0100-0-0200	4	8	Rect.	(4)
2DZ4	2.35	32	4512-3-5400	5	3	4.4/6.7	
2E5	2.8	0	1Y54-3-2000	3	6		
B=0, 90 Degrees; B=8, Shadow Closed							
2EA5	2.35	9	5321-4-6300	4	3	5.2/8.0	
2EG4	1.4	0	4531-2-0000	8	4	7.2/11.0	*
*Adapter CI							
2GU5	2.35	4	5312-4-6300	5	4	7.2/11.	
2HK5	2.35	6	5312-4-0300	5	4	9.8/15.	
2HQ5	2.35	6	5312-4-0300	5	4	8.3/12.	
2L2	2.0	5	1000-2-0000	4	8	Rect.	F (6)
Insert Filament Leads in Pins 1 & 5 of In-Line Subminiature Socket.							
2T4	2.35	41	4521-3-5400	8	3	3.9/6.0	
2X2	2.8	9	1000-0-2000	4	8	Rect.	F (6)
2X3	2.8	12	0104-0-0020	6	8	Rect.	F
2Y2	2.8	11	1000-0-2000	4	8	Rect.	F (6)
2Z2	2.8	11	1400-0-2000	5	8	Rect.	F (6)
3A8	1.4	5	2146-X-9100	5	1	.49/.75	F (1)(7)
	-	15	- - -	-	-	.21/.32	F (2)
	-	0	2100-0-0140	11	8	Diode	F (1)
3AT2	3.15	3	1000-0-0002	4	8	Rect.	(6)
Adapter CK							
3AW2	3.15	8	1000-0-0002	4	8	Rect.	
3BL2	3.15	12	0001-0-2000	1	8	Rect.	(6)*
*Adapter CK—Rotate tube so arrow is at pin 6							
3BM2	3.15	10	0001-0-2000	1	8	Rect.	(6)*
*Adapter CK—Rotate tube so arrow is at pin 6							
3C2	1.4	10	0100-2-0100	4	8	Rect.	F (6)
3CN3A	3.15	9	0100-0-0200	4	8	Rect.	(6)
3CU3	3.15	2	0100-0-0200	6	8	Rect.	F(6)
3DZ4	3.15	32	4512-3-5400	5	3	4.4/6.7	
3E29	6.3	5	1563-2-5100	3	4	7.0/14.	(6)
Adapter CG or CM (Connect two plate terminals with jumper)							
3FQ5	2.8	9	3512-4-0300	5	4	8.0/12.	
3GU5	3.15	4	5312-4-6300	5	4	7.2/11.	
3HA5	2.8	8	5312-4-0300	5	4	7.2/11.	
3HK5	3.15	6	5312-4-0300	5	4	9.8/15.	
3HQ5	3.15	6	5312-4-0300	5	4	8.3/12.	
3JC6A	3.15	8	3531-2-0463	5	4	10./15.	
4A6	2.0	21	019X-5-4120	5	1	.58/.90	F (1)(2)
4BL8/	4.7	32	9561-2-438X	1	3	3.6/5.5	(1)
XCF80	-	-	- - -	5	3	2.9/4.4	(3)
4BN4	4.2	14	3512-4-3500	5	3	4.4/6.8	
4BZ8	4.2	8	9X81-2-4530	5	3	5.2/8.0	(1)(3)
4CM4	4.2	8	4531-2-5354	5	4	9.1/14.	

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
-----------	---	---	----------	---	---	---------	-------

4CX300A	6.3	0	1000-0-2000	1	3	7.8/12.0	*
*Use jumpers to connect Plate, Cath. & Grid leads. Connect leads from heater to filament pins in combination socket							
4E17	4.2	10	3531-2-0467	5	4	9.7/15.	
4GK5	4.2	8	3512-4-0300	5	4	7.4/11.5	
4GM6	4.2	9	5312-4-6700	5	4	6.5/10.0	(1)
4GX7	4.2	6	3531-2-469X	5	4	6.5/11.0	(1)
	-	3	- - -	-	3	5.3/8.2	(2)
4GZ5	4.2	5	3512-5-6400	2	3	3.9/7.9	
4HA5	4.2	8	5312-4-0300	5	4	7.2/11.	
4HC7	4.2	18	0052-0-1430	4	2	1.2/1.9	(1)*
*Adapter CK—Rotate tube so arrow is at pin 6							
	-	24	4001-0-2000	-	3	2.9/4.4	(1)
Rotate tube so arrow is at pin 6. Connect B to Grid Cap; connect C to Cath. Cap							
4HK5	4.2	6	5312-4-0300	5	4	9.8/15.	
4HQ5	4.2	0	5312-4-0300	5	4	8.5/13.0	(1)
4HS8	4.2	18	3641-2-7547	5	2	1.3/2.0	
4HT6	4.2	12	3531-2-0467	5	4	7.0/11.0	(1)
4JC6	4.7	8	3531-2-0463	5	4	10./15.	
4JD6	4.7	7	3531-2-0467	5	4	7.0/14.	
4JH6	4.2	5	5312-4-6700	5	3	4.7/8.0	(1)
4KE8	4.7	14	9561-2-438X	5	3	5.9/9.0	(1)
	-	-	- - -	-	-	5.3/8.2	(3)
4LJ8	4.2	5	X931-2-4635	5	4	7.2/11.0	(1)
	-	-	- - -	-	3	5.2/8.0	(1&3)
4-65A	6.3	15	1605-0-6200	2	2	1.2/2.4	(6)
Adapter CG or CM							
5AW4	5.0	12	0109-0-4020	6	8	Rect.	F(1)(2)
5AX4	5.0	11	0109-0-4020	6	8	Rect.	F(1)(2)
5BC3	5.0	12	1020-9-0004	6	8	Rect.	F(1)(2)
Adapter CL—Connect side pin to Plate cap							
5BQ7	5.0	13	9X81-2-4530	5	3	4.2/6.4	(1)(3)
5BS8	6.3	12	4531-2-9X80	5	3	4.7/7.2	(1)(3)
5CM6	4.7	12	6051-2-5304	2	3	2.1/4.1	
5CR8	4.7	5	9531-2-463X	5	3	5.0/7.7	(1)
	-	15	- - -	-	-	2.6/4.0	(2)
5EH8	4.7	8	3X91-2-3564	5	3	3.9/6.0	(1)
	-	9	- - -	-	-	4.9/7.5	(2)
5GJ7	5.0	8	3531-2-469X	5	4	7.1/11.0	(1)
	-	26	- - -	-	3	5.9/9.0	(1&3)
5GX7	5.0	8	3531-2-469X	5	4	7.1/11.	(1)
	-	3	- - -	-	3	4.6/7.1	(2)
5HA7	5.0	5	0051-0-2430	4	2	1.4/2.2	(1)
	-	16	04X1-0-2980	-	-	1.0/1.6	(3)
Adapter CK—Rotate tube so arrow is at pin 6 on both tests							
5HB7	4.7	0	3531-2-4654	6	3	5.5/8.4	(1)
	-	-	- - -	-	-	4.9/7.0	(2)
5HG8	5.0	0	3531-2-X946	5	4	7.8/12.0	(1)
	-	25	- - -	-	3	3.3/5.6	(2)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
5HZ6 ...	5.0	15	5312-4-6700	5	3	2.4/3.5	
5JK8 ...	4.7	0	5312-4-6700	5	4	12.0/18.0	
5JL8 ...	5.0	15	5312-4-6700	5	4	10.0/15.5	(1)
5KE8 ...	6.3	5	9561-2-438X	5	4	8.0/12.	(1)
	-	8	- - -	-	3	5.4/8.0	(3)
5KZ8 ...	5.6	5	9571-2-463X	4	3	4.6/7.0	(1)
	-	-	- - -	-	-	5.6/8.5	(3)
5LJ8 ...	5.0	0	X931-2-4635	5	4	8.5/13.0	(1)
	-	-	- - -	-	3	5.2/8.0	(3)
5W4 ...	5.0	10	0109-0-4020	6	8	Rect.	F (1)(2)
5X3 ...	5.0	11	1940-0-2000	6	8	Rect.	F (1)(2)
6A3 ...	6.3	11	1450-0-2000	6	3	2.3/4.5	F
6A4 ...	6.3	8	1450-6-2000	6	2	1.1/2.2	F
6A6 ...	6.3	5	19X3-5-4200	2	2	1.0/1.8	(1)(2)
6AC6 ..	6.3	0	0146-5-0230	4	2	1.5/2.4	
6AC10 ..	6.3	15	1300-0-0542	4	3	3.6/5.5	(1)
	-	-	1043-5-0002	-	-	-/-	(1)
	-	0	1000-0-0002	-	-	-/-	(1)
Adapter CK—Test 3 Connect A to Plate Cap; connect B to Cath. Cap; connect C to Grid Cap							
6AD6 ...	6.3	0	0155-6-0230	3	6		
B=0, 90 Degrees; B=50, Shadow 30 Degrees							
6AD7 ...	6.3	15	X146-5-9270	2	2	1.3/2.5	F (1)
	-	20	- - -	2	1	.21/.32	(2)
6AD10 ..	6.3	0	1070-9-5362	6	3	4.6/6.6	
Adapter CK—Connect A to Cath. Cap; connect B to Grid Cap; connect C to Plate Cap							
6AE5 ...	6.3	15	0140-5-0230	6	2	.78/1.2	
6AE6 ...	6.3	18	0104-5-0230	1	1	.61/.95	(1)
	-	-	0140-5-0230	1	1	.61/.95	(1)
6AE7 ...	6.3	14	0145-3-0200	2	2	.97/1.5	(1)
	-	-	0140-0-X280	-	-	.97/1.5	(3)
6AG9 ...	6.3	8	1400-0-0362	4	4	19.6/30.0	
	-	14	1053-4-0002	5	3	3.0/4.6	
Adapter CK							
6AH9 ..	6.3	33	0001-0-2X90	5	3	1.7/2.7	(3)
Adapter CK—Rotate tube so arrow is at pin 6. Connect C to Cath. Cap							
	-	0	5670-4-1020	-	4	13.0/21.0	(1)
Adapter CK—Rotate tube so arrow is at pin 4. Connect B to Cath. Cap							
6AJ7 ...	6.3	14	0175-3-6240	4	3	5.5/8.4	
6AK4 ...	6.3	9	5010-3-2040	3	3	2.5/3.8	
6AK7 ...	6.3	4	7105-3-6240	4	4	5.5/11.	
6AL11 ..	6.3	7	1000-0-5362	2	3	4.6/6.5	(1)
Adapter CK. Connect lead from C to Plate Cap							
	-	25	1704-6-0002	5	2	.65/1.0	(1)
Connect leads from A to Cath Cap; B to Grid Cap							
6AM5 ..	6.3	12	5312-4-0600	2	2	1.3/2.6	
6AU7 ..	3.15	9	4531-1-9X82	2	2	1.3/1.9	(1)(3)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
6AY11 ..	6.3	19	1354-9-X802	4	2	1.2/1.9	(1) (3)
			Adapter CK				
		0	0431-0-2890	11	8	Diode	(1) (3)
6BA3 ...	6.3	13	0401-2-0403	6	8	Rect.	
			Adapter CL				
6B4	6.3	40	0140-5-0200	2	3	2.2/4.3	F
6B5	6.3	15	1465-3-2000	1	2	1.4/2.4	
6B6	6.3	23	0140-0-0230	1	2	.71/1.0	(1)(7)
		0	0104-9-0230	11	8	Diode	(1)(2)
6B7	6.3	42	1460-0-3200	5	2	.62/.95	(1)(7)
		0	1004-9-3200	11	8	Diode	(1)(2)
6BA5 ...	6.3	21	5020-4-1630	5	2	1.4/2.2	
6BD4A ..	6.3	0	3100-4-0200	11	8	Diode	(6)
6BD11 ..	6.3	10	1000-0-0362	5	4	6.5/10.	(1)
			Adapter CK—Connect leads from A to Plate cap; C to Grid cap				
			148X-3-9002	-	3	2.6/4.0	(1) (3)
			Connect lead from B to Grid Cap				
6BE3 ...	6.3	0	1400-3-0042	11	8	Diode	
			Adapter CK				
6BE7 ...	6.3	13	6531-2-4535	4	2	.78/1.2	
6BF11 ..	6.3	37	1000-0-5362	5	3	4.3/8.6	(1)
			Adapter CK—Connect lead from C to Plate Cap				
		23	1076-4-0002	-	2	.65/1.0	(1)
			Connect leads from A to Cath Cap; B to Grid Cap				
6BJ3	6.3	0	1400-3-0042	11	8	Diode	
			Adapter CK				
6BL4 ...	6.3	15	0030-4-0210	6	8	Rect.	(1)
6BT6 ...	6.3	14	5312-0-0400	5	2	.85/1.3	(1)
		0	0312-4-9000	11	8	Diode	(1)(2)
6BT8 ...	6.3	17	0001-2-4653	4	3	4.0/6.2	(1)
		0	9431-2-0000	11	8	Diode	(1)(2)
6BV11 ..	6.3	15	1000-5-3642	5	3	2.4/3.7	(1)
			Adapter CK—Connect C to Grid Cap				
			0102-7-4630	-	-	-/-	(1)
			Adapter CK—Rotate tube so arrow is at pin 8. Connect C to Grid Cap				
6BW11 .	6.3	5	1000-7-4632	5	3	5.5/8.5	(1)
			Adapter CK—Connect C to Grid Cap				
			1647-0-0002	-	4	7.6/13.0	(1)
			Adapter CK—Connect A to Cath. Cap; connect B to Grid Cap				
6BX8 ...	6.3	23	4531-2-9X80	5	3	4.0/6.1	(1)(3)
6C7	6.3	10	1400-0-3200	2	2	.78/1.2	(1)(7)
		0	1009-4-3200	11	8	Diode	(1)(2)
6CG3 ...	6.3	0	3401-0-2000	11	8	Rect.	(1)
			Adapter CK—Rotate tube so arrow is at pin 6				
6CH7 ...	6.3	14	9X81-2-4533	5	3	4.4/6.8	(1)(3)
6CJ3	6.3	0	0401-2-0403	11	8	Diode	(1)
			Adapter CL				

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
6CK3 ...	6.3	0	0401-2-0403 Adapter CL	11	8	Diode	(1)
6CL3 ...	6.3	20	0401-2-0403	6	8	Rect.	
6CM3 ..	6.3	14	0401-2-0403	5	8	Rect.	(1)
6CQ4 ...	6.3	13	0030-4-0120	5	8	Rect.	(1)
6CR8 ...	6.3	5	9531-2-463X	5	3	5.0/7.7	(1)
	-	15	- - -	-	-	2.6/4.0	(2)
6D7	6.3	39	1467-0-3200	4	2	.78/1.2	(7)
6D8	6.3	50	0146-5-4230	5	2	.80/1.6	(7)
6DS4 ...	6.3	1	4531-2-0000	9	3	5.3/8.2	
			Below serial #3000 use Adapter CL				
6DX8 ...	6.3	40	X981-2-4356	1	4	6.4/9.8	(1)
	-	6	- - -	5	3	2.6/4.0	(3)
6DW4 ..	6.3	14	0401-2-0403	6	8	Rect.	
			Adapter CL—Connect side pin to Cath. Cap				
6DY7 ...	6.3	16	5146-5-4230	2	3	3.0/6.0	
6DZ4 ...	6.3	32	4512-3-5400	5	3	4.4/6.7	
6E6	6.3	27	19X3-5-4200	2	2	1.1/1.7	(1)(2)
6E7	6.3	33	1467-0-3200	4	2	1.0/1.6	(7)
6EC7 ...	6.3	17	3531-2-0467	5	3	2.8/4.4	
6EF6 ...	6.3	20	0146-5-0230	2	3	2.0/4.0	
6ET7 ...	6.3	10	0001-2-3564	5	4	7.5/11.5	
	-	0	3941-2-0000	11	8	Diode	(1)(2)
6FD6 ...	6.3	9	5712-4-6300	11	2	.98/1.5	
6FE5 ...	6.3	9	0146-5-0230	6	3	4.7/9.5	
6FG5 ...	6.3	1	5312-4-6300	1	3	6.7/9.5	
6FH6 ...	6.3	21	0106-5-0230	3	3	2.5/5.0	(6)
6FM7 ...	6.3	29	1090-8-X352	4	2	1.7/2.2	(1)
	-	11	- - -	6	3	2.8/5.6	(3)
			Adapter CK—Connect Plate Cap to C				
6FW5 ..	6.3	15	5130-4-0260	3	3	3.3/6.6	
6FY7	6.3	29	8541-0-20X9	4	2	1.0/1.6	(1)
	-	12	- - -	6	3	3.6/5.4	(3)
			Adapter CK—Rotate tube so that arrow is at pin 6 Connect B to Cath. Cap				
6GA8 ..	6.3	8	9X81-2-4530	2	3	2.2/3.4	(1)(3)
6GB5 ...	6.3	12	5531-2-6630	6	3	4.1/8.2	(6)
			Adapter CL				
6GC6 ...	6.3	13	0136-5-0260	3	3	3.8/7.5	(6)
6GJ5 ...	6.3	18	6531-2-5600	3	3	3.0/6.0	(6)
			Adapter CL				
6GJ7/ ..	6.3	9	3531-2-469X	5	4	7.2/11.	(1)
ECF801	-	29	- - -	-	3	6.0/9.0	(2)
6GM5 ...	6.3	8	6001-2-5304	2	4	5.0/10.	
6GT5 ...	6.3	16	6531-2-5604	3	3	3.4/6.8	
			Adapter CL—Connect Plate Cap to side pin on Adapter				
6GU5 ...	6.3	4	5312-4-6300	5	4	7.2/11.	
6GV5 ...	6.3	17	1350-6-0032	3	3	4.0/6.1	(6)
			Adapter CK				

TUBE TYPE	A	B	ELEMENTS	C	D	REI/AVG	NOTES
6GX7 ...	6.3	8	3531-2-469X	5	4	7.0/10.7	(1)
	-	3	- - -	-	3	4.6/7.1	(2)
6GY5 ...	6.3	13	1350-6-0532	6	3	4.0/8.0	(6)
			Adapter CK				
6H4	6.3	12	0104-0-0230	6	8	Rect.	
6H7M ..	6.3	18	0146-5-0320	2	2	1.5/2.2	(1)
	-	12	0100-0-4320	1	1	.20/.30	(1)(7)
6H7S ...	6.3	18	1465-0-3200	2	2	1.5/2.2	(1)
	-	12	1000-4-3200	1	1	.20/.30	(1)(7)
6HA5/ EC900	6.3	8	5312-4-0300	5	4	7.2/11.	
6HB5 ...	6.3	12	4351-0-2650	6	3	4.4/8.8	
			Adapter CK—Rotate tube so arrow is at pin 6				
6HD5 ...	6.3	15	1360-4-0632	6	4	4.5/9.0	
			Adapter CK—Connect lead from B to Grid Cap				
6HE5 ...	6.3	18	1304-0-0562	2	3	2.0/4.1	
			Adapter CK				
6HF5 ...	6.3	18	1356-0-6532	6	3	3.5/7.0	(6)
			Adapter CK				
6HG5 ...	6.3	13	5312-4-6500	2	3	2.1/4.1	
6HG8	6.3	5	3531-2-X946	5	4	7.8/12.	(1)
	-	31	- - -	-	3	3.6/5.5	(2)
6HK5 ...	6.3	6	5312-4-0300	5	4	9.8/15.	
6HM6 ...	6.3	6	3531-2-0467	5	4	10./15.	
6HQ5 ...	6.3	6	5312-4-0300	5	4	8.3/12.	
6HR5 ...	6.3	10	5312-4-6500	2	3	2.9/4.1	(1)
6HR6 ...	6.3	9	5712-4-6300	4	3	5.0/7.6	
6HS5	6.3	5	4651-0-2560	1	4	16.0/25.0 *	
			*Adapter CK—Rotate tube so arrow is at pin 6				
6HU6 ...	6.3	15	5031-2-6704	5	2	.78/1.2	(1)
6HV5 ..	6.3	0	1300-4-0002	1	4	9.8/15.0	
			Adapter CK—Connect A to Grid Cap				
6HW8 ..	6.3	38	3461-2-5343	1	3	2.6/4.0	
6HZ6 ...	6.3	11	5312-4-6700	5	3	2.2/3.4	
6J8	6.3	25	0146-5-4230	5	2	1.2/2.4	(7)
6J10	6.3	35	1476-5-3002	5	1	.40/.60	(1)
	-	7	0051-0-2630	2	3	4.5/6.5	(1)
			Adapter CK—for second test rotate tube so arrow is at pin 6. Connect lead from B to Plate Cap				
6JB6	6.3	20	6531-2-5670	3	3	2.5/5.0	(6)
			Adapter CL				
6JC6	6.3	8	3531-2-0463	5	4	10./15.	
6JD6	6.3	7	3531-2-0467	5	4	7.0/14.	
6JE6	6.3	20	6531-2-5670	6	4	4.5/6.9	(6)
			Adapter CL				
6JF6 ...	6.3	20	6531-2-5670	6	4	6.5/10.0	
6JH6	6.3	7	5312-4-6700	5	3	5.2/8.0	
6JN8	6.3	7	X981-2-4635	5	3	5.0/7.5	(1)
	-	-	- - -	-	-	5.5/8.5	(3)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
6JQ6 ...	6.3	8	4061-2-9553	6	3	2.7/4.2	(1)
	-	0	- - -	11	8	Diode	(3)
6JU8	6.3	0	4301-2-0980	11	8	Diode	(1)(3)
	-	-	0431-2-0098	11	8	-	(1)(3)
6JV8	6.3	4	8X91-2-3564	5	4	5.5/11.	(1)
	-	24	- - -	4	3	2.6/4.0	(3)
6JW8/ ..	6.3	10	9561-2-438X	5	3	3.4/5.3	(1)
ECF802	-	-	- - -	-	-	2.3/3.6	(3)
6JX8	6.3	23	5531-2-469X	8	1	.42/.60	(1)
	-	3	- - -	9	2	1.8/2.8	(3)
6K4	6.3	18	4510-0-2030	5	3	3.3/5.0	
6KA8 ...	6.3	12	9X31-2-5764	5	3	2.9/4.4	(1)
	-	26	- - -	4	-	2.6/4.0	(2)
6KD6 ...	6.3	13	0061-0-2365	6	4	9.1/14.0	(1)(6)*
*Adapter CK—Rotate tube so arrow is at pin 6. Connect B to Grid Cap							
6KL8 ...	6.3	13	7531-2-6490	5	3	2.8/4.0	(1)
	-	0	- - -	11	8	Diode	(3)
6KM8 ...	6.3	0	4491-2-3564	5	3	2.9/4.4	
	-	25	- - -	-	8	Diode	(2)
6KN6 ...	6.3	6	0001-0-2365	6	4	10.0/16.0	(1)
6KT6 ...	6.3	5	3531-2-0467	5	4	11.8/18.0	(1)
6KV8 ...	6.3	15	8X91-2-3564	5	4	14.8/21.0	(1)
	-	10	- - -	-	3	2.6/4.0	(3)
6KZ8	6.3	4	9531-2-468X	5	3	5.0/7.5	(1)
	-	10	- - -	-	-	5.5/8.5	(3)
6L5	6.3	38	0140-5-0230	5	2	.98/1.5	
6LB6 ...	6.3	24	0102-3-6750	8	4	9.4/13.4	*
*Adapter CK—Rotate tube so arrow is at pin 8							
6LB8 ...	6.3	17	8X91-2-3564	4	4	10./20.	(1)
	-	12	- - -	5	3	3.2/5.0	(3)
6LJ8	6.3	3	X931-2-4645	5	4	8.5/13.0	(1)
	-	10	- - -	-	3	5.2/8.0	(3)
6LM8 ...	6.3	12	9561-2-438X	5	3	4.5/6.5	(1)
	-	-	- - -	-	-	3.9/6.0	(3)
6LN8	6.3	10	9561-2-438X	5	3	4.0/6.2	(1)
	-	22	- - -	-	-	3.6/5.6	(3)
6LQ6 ...	6.3	34	6531-2-5670	8	3	4.9/7.5	*
Adapter CL							
6LQ8 ...	6.3	11	8X91-2-3564	4	4	15.0/23.0	(1)
	-	17	- - -	-	-	6.7/10.4	(3)
6LT8 ...	6.3	8	3641-2-7005	5	4	8.5/13.0	(1)
	-	0	0001-2-4390	11	8	Diode	(1)(2)
6LU8 ...	6.3	15	0531-0-2400	4	3	6.0/9.3	(1)
Adapter CK—Rotate tube so arrow is at pin 6							
	-	5	5001-0-2000	-	-	2.5/3.6	(1)
Connect B to Cath. Cap; connect C to Plate Cap							
6LX8 ...	6.3	16	9561-2-438X	5	3	3.6/5.5	(1)
	-	26	- - -	4	-	2.3/3.5	(3)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
6LY8 ...	6.3	12	8X91-2-3564	5	4	13.0/20.0	(1)
	-	-	- - -	-	2	1.1/1.7	(3)
6M8 ...	6.3	37	3146-X-9200	5	2	1.2/1.9	(1)(7)
	-	12	- - -	-	-	.72/1.1	(2)
	-	0	3100-0-0240	11	8	Diode	(1)
6MD8 ...	6.3	10	0941-2-53X0	2	3	2.0/3.1	(1)(2)
	-	-	4001-2-0305	-	-	2.0/3.1	
			Adapter CL				
6ME8 ..	6.3	10	4441-2-5344	5	3	3.1/4.4	
6MF8 ...	6.3	15	0531-0-2400	5	3	2.7/4.1	(1)
			Adapter CK—Rotate tube so arrow is at pin 6				
	-	6	1405-5-6302	6	-	-/-	(1)
			Adapter CK				
6MJ8 ...	6.3	33	05X1-0-2430	5	3	1.9/3.0	(1)
	-	-	3405-0-0012	-	-	-/-	(1)
6N4	6.3	16	5321-4-3500	5	3	3.9/6.0	
6N6	6.3	15	0146-5-0230	1	2	1.4/2.4	
6P5	6.3	6	0140-5-0230	6	2	.71/1.1	
6P7	6.3	5	0124-6-9X30	3	2	.71/1.1	(1)(7)
	-	10	- - -	5	1	.29/.45	(2)
6Q6	6.3	10	0140-9-0230	5	2	.65/1.0	(1)(7)
	-	0	- - -	11	8	Diode	(2)
6R4	6.3	20	5031-2-0040	5	3	3.1/4.6	
6S6	6.3	22	6104-0-0230	4	3	2.6/4.0	(7)
6S7	6.3	17	0146-7-0230	4	2	1.1/1.7	(7)
6S78 ...	6.3	9	X985-4-3210	2	3	2.3/3.5	(1)(3)
6ST7 ...	6.3	10	0530-0-4210	2	2	1.2/1.9	(1)
	-	-	0039-4-0210	11	8	Diode	(1)(2)
6SZ7 ...	6.3	31	0530-0-4210	1	2	.78/1.2	(1)
	-	0	0039-4-0210	11	8	Diode	(1)(2)
6T6	6.3	12	0146-0-0230	4	3	3.6/5.5	(7)
6T7	6.3	29	0140-0-0230	1	2	.65/1.0	(1)(7)
	-	0	0109-4-0230	11	8	Diode	(1)(2)
6T10	6.3	7	1000-0-5362	2	3	4.2/6.5	(1)
			Adapter CK—Connect lead from C to Plate Cap				
	-	18	1076-4-0002	5	2	.91/1.4	(1)
			Connect lead from B to Grid Cap; A to Cath Cap				
6U3	6.3	14	0032-1-0004	5	8	Rect.	
6U7	6.3	37	0146-7-0230	5	2	.98/1.5	(7)
6U10 ...	6.3	8	1800-0-0X92	3	2	1.5/2.3	(1)(3)
	-	19	1043-5-0002	4	-	1.0/1.6	(1)
			Adapter CK—For test 1 connect leads from A to Plate Cap; B to Cath Cap; C to Grid Cap				
6V7	6.3	8	0140-0-0230	6	2	.72/1.1	(1)(7)
	-	0	0109-4-0230	11	8	Diode	(1)(2)
6W7	6.3	36	0146-7-0230	4	2	.80/1.2	(7)
6Y5	6.3	13	1093-4-2000	6	8	Rect.	(1)(2)
6Y7	6.3	20	019X-5-4230	1	2	1.0/1.5	(1)(2)
6Z4	6.3	12	1940-3-2000	6	8	Rect.	(1)(2)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
6Z5	6.3	14	2193-4-1000	6	8	Rect.	(1)(2)
6Z7	6.3	0	019X-5-4230	5	2	.84/1.3	(1)(2)
6Z10	6.3	15	0051-0-2630	5	3	4.2/6.5	(1)
Adapter CK—Rotate tube so arrow is at pin 6. Connect B to Plate Cap							
	-	22	2476-5-3001	-	1	.5/.7	(2)
6ZY5	6.3	12	0190-4-0230	6	8	Rect.	(1)(2)
7A4	6.3	12	1400-0-5320	5	3	2.0/3.0	
7A5	6.3	7	1460-0-5320	6	3	2.9/5.8	
7A6	6.3	11	1890-0-4320	6	8	Rect.	(1)(3)
7A7	6.3	11	1467-0-5320	5	2	1.5/2.4	
7AB7	6.3	19	6143-5-3230	4	2	1.2/1.8	
7AD7	6.3	11	1463-3-5320	4	4	6.2/9.5	
7AF7	6.3	9	189X-5-4320	2	2	1.4/2.2	(1)(3)
7AG7	6.3	21	1463-3-5320	1	3	2.7/4.2	
7AH7	6.3	19	1467-0-5320	1	3	2.1/3.3	
7AJ7	6.3	41	1463-3-5320	4	2	1.0/1.6	
7A8	6.3	50	1445-6-5320	4	2	1.0/2.0	
7B4	6.3	12	1400-0-5320	5	2	.78/1.2	
7B5	6.3	9	1460-0-5320	6	2	.98/1.5	
7B6	6.3	11	1450-0-0320	5	1	.59/.90	(1)
	-	0	1000-9-4320	11	8	Diode	(1)(2)
7B7	6.3	45	1463-3-5320	5	2	1.1/1.7	
7B8	6.3	5	1445-6-5320	6	2	.80/1.6	
7C5	6.3	14	1460-0-5320	2	3	2.1/4.1	
7C6	6.3	0	1453-0-0320	8	1	.55/.85	(1)
	-	-	1003-9-4320	11	8	Diode	(1)(2)
7C7	6.3	13	1467-0-5320	5	2	1.5/2.3	
7DJ8	7.5	21	9X81-2-4531	5	4	8.4/13.0	(1)(3)
7E6	6.3	34	1453-0-0320	5	2	.98/1.5	(1)
	-	0	1003-4-9320	11	8	Diode	(1)(2)
7E7	6.3	25	1400-6-5320	5	2	1.0/1.6	(1)
	-	0	1049-0-0320	11	8	Diode	(1)(2)
7ED7	7.5	8	3531-2-0467	5	3	5.7/8.8	
7G7	6.3	24	1463-3-5320	4	3	2.9/4.5	
7G8	6.3	27	196X-5-3420	4	2	1.4/2.1	(1)(2)
This set up to be used on tester above serial #5000							
7G8*	6.3	20	196X-5-3420	4	2	1.4/2.1	(1)(2)
* This set up must be used on tester below serial #5000							
7L7	6.3	21	1467-0-5320	5	2	2.0/3.0	
7Q7	6.3	20	1465-7-5320	4	2	.80/1.6	
7R7	6.3	14	1400-6-5320	5	2	2.0/3.0	(1)
	-	0	1094-0-0320	11	8	Diode	(1)(2)
7S7	6.3	30	1405-8-5320	4	2	1.0/2.0	(1)
	-	-	1045-0-0320	5	-	.71/1.1	(1)
8AR11	6.3	2	1000-7-4652	5	4	6.5/10.0	(1)
	-	-	0201-4-8750	-	-	-/-	(1)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
8B10	8.4	8	14X9-8-0002	2	2	1.6/2.5	(1)(3)
	-	0	1000-0-4392	11	8	Diode	(1)(2)
Adapter CK—For test 1 connect A to Cath. Cap; B to Grid Cap							
8BA11	8.4	41	0341-0-2000	5	2	1.1/1.7	(1)*
*Adapter CK—Rotate tube so arrow is at pin 6. Connect B to Grid Cap							
	-	0	0001-0-2467	-	-	.85/1.3	(1)
Adapter CK—Rotate tube so arrow is at pin 6. Connect A to Cath. Cap; connect C to Grid Cap							
	-	-	6473-0-0012	-	-	-/-	(1)
Adapter CK—Rotate tube so arrow is at pin 2. Connect A to Grid Cap							
8BM11	8.4	9	1000-4-7632	5	3	5.5/8.5	(1)
Adapter CK—Connect C to Grid Cap							
	-	7	0102-4-6730	-	-	5.7/8.8	(1)
Adapter CK—Rotate tube so arrow is at pin 8. Connect C to Grid Cap							
8BN11	8.4	8	1000-5-3672	5	4	8.5/13.0	(1)
Adapter CK—Connect C to Plate Cap							
	-	-	1647-0-0002	-	-	-/-	(1)
Adapter CK—Connect A to Cath. Cap; connect B to Grid Cap							
8BQ11	8.4	8	1000-7-4652	5	4	6.8/10.5	(1)
Adapter CK—Connect C to Cath. Cap							
	-	-	0102-4-6750	-	-	8.5/13.	(1)
Rotate tube so arrow is at pin 8. Connect lead from C to Cath. Cap							
8BU11	7.5	0	108X-9-5642	4	3	4.9/7.5	(1)
Adapter CK—Connect B to Cath. Cap							
	-	7	- - -	5	-	5.5/8.6	(3)
Adapter CK							
	-	4	0010-2-3450	-	-	-/-	(1)
Adapter CK—Rotate tube so arrow is at pin 7							
8CW5	8.4	5	0531-2-0406	6	4	7.2/10.0	
8CY7	8.4	30	90X1-2-4538	4	2	.85/1.3	(1)
	-	13	- - -	6	3	3.5/5.4	(3)
8GJ7	8.4	9	3531-2-469X	5	4	7.2/11.	(1)
	-	29	- - -	-	3	6.0/9.0	(2)
8GU7	8.4	37	9X81-2-4530	5	3	2.0/3.1	(1)(3)
8GX7	8.4	8	3531-2-469X	5	4	7.0/10.7	(1)
	-	3	- - -	-	3	4.6/7.1	(2)
8HG8	8.4	5	3531-2-X946	5	4	7.8/12.0	(1)
	-	31	- - -	-	3	3.6/5.5	(2)
8JE8	8.4	42	8X91-2-3564	1	4	6.0/12.0	(1)
	-	27	- - -	4	3	2.7/4.2	(3)
8JK8	8.4	11	9X81-2-4530	5	3	3.9/6.0	(1)
	-	10	- - -	-	4	8.5/13.0	(3)
8JT8	8.4	17	8X91-2-3564	5	4	13.6/20.8	(1)
	-	19	- - -	4	2	1.3/2.0	(3)
8JU8A	8.4	0	4301-2-0980	11	8	Diode	(1)(3)
	-	-	0431-2-0098	-	-	-/-	(1)(3)

TUBE TYPE	A	B	ELEMENTS	C	D	REI/AVG	NOTES
8IV8 ...	8.4	4	8X91-2-3564	5	4	5.5/11.0	(1)
	-	24	---	4	3	2.6/4.0	(3)
8KA8 ...	8.4	12	9X31-2-5764	5	3	2.9/4.4	(1)
	-	26	---	4	-	2.6/4.0	(2)
8LE8 ...	8.4	24	4731-2-0065	5	3	3.8/5.8	(1)
	-	-	0031-2-4765	-	-	-/-	(1)
9DZ8 ...	9.5	6	0351-2-4600	6	3	3.8/7.5	(1)
	-	13	X001-2-0089	5	2	.91/1.4	(3)
9EA8 ...	9.5	9	9561-2-438X	5	3	4.2/6.4	(1)
	-	5	---	-	-	6.0/9.2	(3)
9EF6 ...	9.5	20	0146-5-0230	2	3	2.0/4.0	
9GB8 ..	9.5	11	9X81-2-4653	5	3	4.8/7.5	(1)
	-	12	---	2	2	2.2/3.4	(3)
9GV8 ...	9.5	7	9X81-2-4635	6	3	4.8/7.4	(1)
	-	-	---	5	-	3.8/5.8	(3)
9KC6 ...	8.4	6	3501-2-7406	4	4	15.6/24.0	(1)
9KX6 ...	8.4	11	3571-2-0467	4	4	24.0/30.0	(1)
9KZ8 ...	9.5	5	9531-2-468X	5	3	4.9/7.5	(1)
	-	-	---	-	-	5.6/8.5	(3)
9LA6 ...	8.4	21	3571-2-0467	5	4	14.0/21.0	(1)
9X8	9.5	8	7X92-1-3564	4	3	3.0/4.6	(1)
	-	11	---	5	-	3.8/5.8	(2)
10	7.5	22	1450-0-2000	3	2	.91/1.4	F
10CW5 ..	10.5	7	0531-2-0406	3	4	6.5/10.	
10DX8 ..	10.5	25	5431-2-4356	5	3	2.6/4.0	(1)
	-	-	---	1	4	7.1/11.0	(1)
10EC7 ..	12.6	17	3531-2-0467	5	3	2.8/4.4	
10EW7 ..	9.5	10	9XX1-2-4538	2	2	1.3/2.0	(1)
	-	-	---	6	3	3.8/7.5	(3)
10FD7 ..	10.5	29	9XX1-2-4538	4	2	1.0/1.6	(1)
	-	9	---	6	3	3.8/7.5	(3)
10GF7A ..	9.5	10	3X81-2-9045	5	2	1.0/1.6	(1)
	-	13	---	6	3	4.7/7.2	(3)
10GK6 ..	10.5	6	3571-2-0467	2	4	5.5/11.0	
10JT8 ...	10.5	17	8X91-2-3564	5	4	13.6/20.8	(1)
	-	19	---	4	2	1.3/2.0	(3)
10JY8 ...	10.5	19	8X91-2-3564	4	4	5.5/11.	(1)
	-	7	---	5	3	6.0/9.2	(3)
10KR8 ..	10.5	18	8X91-2-3564	5	4	13.0/20.0	(1)
	-	8	---	-	-	7.3/10.4	(3)
10LB8 ..	10.5	15	8X91-2-3564	5	4	13.0/20.0	(1)
	-	21	---	-	3	3.2/5.0	(3)
10LE8 ..	10.5	20	9X31-2-4765	5	3	3.8/5.8	
10LZ8 ..	10.5	20	8X91-2-3564	5	3	6.2/9.5	(1)
	-	10	---	-	2	1.3/2.1	(3)
10Y	7.5	19	1450-0-2000	2	2	1.0/1.6	F

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
-----------	---	---	----------	---	---	---------	-------

11BQ11	10.5	5	1000-7-4652	5	4	7.2/11.	(1)
			Adapter CK—Connect C to Cath. Cap				
		3	0102-4-6750	-	-	8.5/13.	(1)
			Rotate tube so arrow is at pin 8.				
			Connect lead from C to Cath. Cap				
11BT11	10.5	18	5306-5-1020	5	4	12.2/19.0	(1)
			Adapter CK—Rotate tube so arrow is at pin 4. Connect A to Cath. Cap; connect C to Plate Cap				
		16	9102-5-X854	-	3	3.6/5.5	(3)
			Adapter CK—Rotate tube so arrow is at pin 8. Connect A to Cath. Cap				
		-	4102-X-5389	-	-	3.4/5.3	(1)
			Adapter CK—Rotate tube so arrow is at pin 8. Connect A to Cath. Cap				
11CS ...	12.6	7	3512-5-6400	6	3	2.9/5.8	
11CA11	10.5	8	198X-3-0002	5	3	3.6/5.5	(1)
			Adapter CK—Connect A to Plate Cap; connect B to Grid Cap				
		14	- - -	-	-	4.0/6.3	(3)
			Adapter CK—Connect A to Plate Cap; connect B to Grid Cap				
		18	0536-4-1020	-	4	12.6/21.2	(1)
			Adapter CK—Rotate tube so arrow is at pin 4				
11FY7 ..	10.5	29	8541-0-20X9	4	2	1.0/1.6	(1)
		12	- - -	6	3	3.6/5.4	(3)
			Adapter CK—Rotate tube so arrow is at pin 6. Connect B to Cath. Cap				
11HM7	5.0	0	3571-1-2467	4	4	19.6/30.0	(1)
11JE8	10.5	42	8X91-2-3564	1	4	6.0/12.0	(1)
		27	- - -	4	3	2.7/4.2	(3)
11KV8 ..	10.5	7	8X91-2-3564	5	4	11./23.	(1)
		24	- - -	4	3	2.6/4.0	(3)
11LQ8	10.5	15	0001-2-3564	5	4	13.8/21.2	
		7	3541-2-0000	-	-	6.5/10.0	
12A	5.0	12	1450-0-2000	6	1	1.2/1.9	F
12A5 ...	6.3	14	1465-3-2100	6	2	1.5/2.3	
12A8 ...	12.6	50	0146-5-4230	5	2	.80/1.6	(7)
12AE10	12.6	6	1000-0-5362	6	3	3.7/5.6	(1)
			Adapter CK—Connect C to Plate Cap				
		0	1078-4-0002	5	2	.65/1.0	(1)
			Adapter CK—Connect A to Grid Cap; connect B to Cath. Cap				
12B8 ...	12.6	30	3146-9-82X0	5	2	1.2/1.8	(1)(7)
		0	- - -	-	-	1.3/2.0	(3)
12BF11	12.6	42	1000-0-5362	5	3	6.4/9.8	(1)
			Adapter CK—Connect lead from C to Plate Cap				
		25	1076-4-0002	-	2	.9/1.4	(1)
			Adapter CK—Connect lead from A to Cath. Cap; B to Grid Cap				
12BK6 ..	12.6	20	5312-0-0400	1	2	1.0/1.8	(1)
		0	0312-9-4000	11	8	Diode	(1)(2)
12BT3 ..	12.6	0	1400-3-0042	11	8	Diode	

Adapter CK

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
12BT8 ..	12.6	13	5312-0-0400	8	2	.84/1.3	(1)
	-	0	0312-4-9000	11	8	Diode	(1)(2)
12BV7 ..	6.3	9	3571-1-2467	4	4	8.5/13.	
12BV11 ..	12.6	15	1000-5-3642	5	3	2.4/3.7	(1)
	-	-	Adapter CK—Connect C to Grid Cap				
	-	-	0102-7-4630	-	-	-/-	(1)
	-	-	Adapter CK—Rotate tube so arrow is at pin 8. Connect C to Grid Cap				
12BZ6 ..	12.6	20	5312-4-6700	4	3	4.0/6.1	(1)
12C8 ...	12.6	30	0140-0-6230	4	2	.84/1.3	(1)(7)
	-	0	0109-4-0230	11	8	Diode	(1)(2)
12CM6 ..	12.6	12	6051-2-5304	2	3	2.1/4.1	
12CK3 ..	12.6	0	0401-2-0403	11	8	Diode	(1)
	-	-	Adapter CL				
12DA6 ..	12.6	6	0531-2-0463	4	3	3.1/4.8	
12DF5 ..	6.3	11	9081-1-4032	5	8	Rect.	(1)(3)
12DK6 ..	12.6	5	5312-4-6700	5	4	6.4/9.8	(1)
12DM4 ..	12.6	14	0030-4-0120	6	8	Rect.	(1)
12DT7 ..	6.3	21	9X81-1-4532	1	2	.85/1.3	(1)(3)
12DW5 ..	12.6	16	6051-2-5304	3	3	2.8/5.5	
12DZ8 ..	12.6	6	0351-2-4600	6	3	3.8/7.5	(1)
	-	14	X001-2-0089	5	2	.91/1.4	(3)
12E5 ...	12.6	6	0140-5-0230	6	2	.98/1.5	
12F5 ...	12.6	12	0104-0-0230	5	2	.72/1.1	(7)
12FR8 ..	12.6	8	0052-1-6400	11	2	1.8/2.7	F(1)
	-	-	5302-1-0094	-	-	.8/1.2	(1)
	-	0	- - -	-	8	Diode	(2)
12FV7 ..	12.6	28	9X81-1-4532	5	3	6.3/9.6	(1)(3)
12FX8 ..	12.6	22	6542-1-X395	11	1	.20/.30	(1)
	-	10	- - -	-	2	.90/1.4	F(2)
12G8 ...	6.3	19	98X1-1-4352	11	2	1.8/2.6	(1)
	-	4	- - -	-	-	-	(3)
12G15 ..	12.6	18	6531-2-5600	3	3	3.0/6.0	(6)
	-	-	Adapter CL				
12GT5 ..	12.6	16	6531-2-5604	3	3	3.4/6.8	
	-	-	Adapter CL—Connect Plate cap to side pin on Adapter				
12HL7 ..	12.6	9	3571-2-0467	5	4	13.7/21.0	
12JN8 ...	12.6	7	X981-2-4635	5	3	5.0/7.5	(1)
	-	-	- - -	-	-	5.5/8.5	(3)
12JQ6 ..	12.6	8	4061-2-9553	6	3	2.7/4.2	(1)
	-	0	- - -	11	8	Diode	(3)
12KL8 ..	12.6	13	7531-2-6490	5	3	2.8/4.0	(1)
	-	0	- - -	11	8	Diode	(3)
12Q7 ...	12.6	14	0140-0-0230	5	2	.78/1.2	(1)(7)
	-	0	0109-4-0230	11	8	Diode	(1)(2)
12S8 ...	12.6	22	0390-8-4210	4	2	.71/1.1	(1)(7)
	-	0	- - -	11	8	Diode	(3)
	-	0	9304-0-0210	-	-	Diode	(1)(2)

TUBE TYPE	A	B	ELEMENTS	C	D	REI/AVG	NOTES
12Z3	12.6	14	1430-0-2000	6	8	Rect.	
13FM7	12.6	29	1090-8-X352	4	2	1.7/2.2	(1)
	-	11	- - -	6	3	2.8/5.6	(3)
Adapter CK—Connect C to Plate Cap							
13GB5	12.6	13	5531-2-6630	6	3	4.1/8.2	(6)
Adapter CL							
14	12.6	7	1460-3-2000	3	2	.65/1.0	(7)
14A4	12.6	12	1400-0-5320	5	3	2.0/3.0	
14A5	12.6	13	1460-0-5320	2	2	1.5/3.0	
14A7	12.6	27	1463-0-5320	5	2	1.2/1.9	
14AF7	12.6	0	189X-5-4320	5	2	1.7/2.6	(1)(3)
14B6	12.6	11	1450-0-0320	5	1	.59/.90	(1)
	-	0	1000-9-4320	11	8	Diode	(1)(2)
14B8	12.6	30	1445-6-5320	4	2	1.2/2.4	
14BR11	12.6	17	0420-1-5630	5	4	5.8/8.9	(1)
Adapter CK—Rotate tube so arrow is at pin 7							
	-	37	1089-3-X452	4	3	2.6/4.0	(1)
	-	25	- - -	-	-	3.7/5.6	(3)
14C5	12.6	14	1460-0-5320	2	3	2.1/4.1	
14C7	12.6	13	1467-0-5320	5	2	1.5/2.3	
14E6	12.6	34	1453-0-0320	5	2	.98/1.5	(1)
	-	0	1003-4-9320	11	8	Diode	(1)(2)
14E7	12.6	25	1400-6-5320	5	2	1.0/1.6	(1)
	-	0	1049-0-0320	11	8	Diode	(1)(2)
14F7	12.6	14	189X-5-4320	5	2	.72/1.1	(1)(3)
14F8	12.6	37	X198-3-4250	4	3	2.2/3.3	(1)(3)
14H7	12.6	17	1463-3-5320	5	3	2.7/4.0	
14I7	12.6	30	1405-6-5320	4	2	.60/1.2	(1)
	-	-	1045-0-0320	5	2	.71/1.1	(1)
14N7	12.6	8	189X-5-4320	3	2	1.8/2.7	(1)(3)
14Q7	12.6	20	1465-7-5320	4	2	.80/1.6	
14R7	12.6	14	1400-6-5320	5	2	2.0/3.0	(1)
	-	0	1094-0-0320	11	8	Diode	(1)(2)
15	2.0	44	1460-3-2000	5	1	.47/.71	(7)
16A8	16.8	40	X351-2-4689	5	3	4.9/7.5	(1)
	-	9	- - -	-	2	1.6/2.5	(1)(3)
16BQ11	16.8	8	1000-7-4652	5	4	6.8/10.5	(1)
Adapter CK—Connect C to Cath. Cap							
	-	-	0102-4-6750	-	-	8.5/13.0	(1)
Adapter CK—Rotate tube so arrow is at pin 8. Connect C to Cath. Cap							
16BX11	16.8	11	18X9-4-5302	5	3	4.1/6.4	(1)(3)
	-	0	0341-0-2560	-	4	7.2/11.0	(1)
Adapter CK—Rotate tube so arrow is at pin 6							
16GY5	16.8	13	1350-6-0532	6	3	4.0/8.0	(6)
Adapter CK							
17	12.6	20	1450-3-2000	2	2	.65/1.0	

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
17BF11	16.8	37	1000-0-5362	5	3	4.3/8.6	(1)
			Adapter CK—Connect lead from C to Plate Cap				
		23	1076-4-0002	-	2	.65/1.0	(1)
			Connect leads from A to Cath Cap; B to Grid Cap				
17BS3	16.8	13	0401-2-0403	6	8	Rect.	
17BZ3	16.8	0	1400-3-0042	11	8	Diode	
17CK3	16.8	0	0401-2-0403	11	8	Rect.	(1)
			Adapter CL				
17EW8	16.8	13	9X81-2-4530	5	3	2.8/4.3	(1)(3)
17JG6	16.8	15	6531-2-7604	6	3	6.5/10.0	
			Adapter CL				
17GJ5	16.8	18	6531-2-5600	3	3	3.0/6.0	(6)
			Adapter CL				
17GT5	16.8	16	6531-2-5604	3	3	3.4/6.8	
			Adapter CL—Connect Plate cap to side pin on Adapter				
17GV5	16.8	17	1350-6-0032	3	3	4.0/6.1	(6)
			Adapter CK				
17JB6	16.8	20	6531-2-5670	3	3	2.5/5.0	(6)
			Adapter CL				
17JK8	16.8	11	9X81-2-4530	5	3	3.9/6.0	(1)
		10	— — —	-	4	8.5/13.0	(3)
17JT6A	16.8	13	6531-2-7604	6	3	4.6/7.1	
17X10	16.8	0	1476-5-3002	6	1	.10/.25	(1)
		3	0051-0-2630	-	3	5.6/8.6	(1)
			Adapter CK Test 2—Rotate tube so arrow is at pin 6. Connect B to Plate Cap				
18AJ10	18.9	4	1000-0-5362	6	3	3.6/5.6	(1)
			Adapter CK—Connect C to Plate Cap				
		9	1076-4-0002	5	2	1.6/2.4	(1)
			Adapter CK—Connect A to Cath. Cap; connect B to Grid Cap				
18GD6A	18.9	0	5712-4-6300	5	3	2.8/4.3	(1)
19	2.0	21	19X5-4-2000	5	2	.65/1.0	F
19BR8	18.9	0	5301-2-0Y04	3	6	-/-	(1)
			Advance B to 15, Eye closes				
19HR6	18.9	9	5712-4-6300	4	3	5.0/7.6	
19HS6	18.9	9	5712-4-6300	5	3	5.3/8.2	
19KG8	18.9	7	9X81-2-4635	5	3	5.3/7.5	(1)
			- - -	-	-	5.5/8.5	(3)
20	3.15	11	1450-0-2000	6	1	.34/.53	F
20EQ7	18.9	0	3531-2-6493	5	3	2.5/3.8	(1)
			- - -	-	-	Diode	(2)
20J8	18.9	33	0143-5-4230	5	2	1.2/2.4	(7)
21KA6	18.9	12	0102-0-6750	6	4	4.5/9.0	(6)
			Adapter CK—Rotate tube so arrow is at pin 8; Connect Cath. Cap to A				
21LR8	18.9	33	8531-2-469X	4	3	2.6/4.0	(3)
		2	- - -	7	-	5.4/8.3	(1)
22	3.15	25	1460-0-2000	8	1	.33/.50	F (7)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
-----------	---	---	----------	---	---	---------	-------

22BW3 ..	26.0	13	1400-3-0042 Adapter CK	6	8	Rect.	
22JG6 ...	18.9	12	6531-2-7604 Adapter CL	6	4	5.0/10.	
22JR6 ..	18.9	14	6531-2-7604 Adapter CL	6	3	4.9/7.0	
22JU6 ...	18.9	0	0031-2-5600	9	4	3.2/5.0	(4)
24A	2.8	6	1460-3-2000	3	2	.68/1.1	(7)
24JE6 ...	26.0	20	6531-2-5670 Adapter CL	6	4	4.5/6.9	(6)
24JZ8 ...	26.0	44	1405-5-6302	5	3	4.8/7.4	
	-	29	1000-0-0052	-	2	1.4/2.1	
Adapter CK Test 2—Connect A to Plate Cap; Connect C to Cath. Cap							
24LQ6 ..	26.0	34	6531-2-5670 Adapter CL	8	3	4.9/7.5	
25A6 ...	26.0	14	0146-5-0230	6	2	1.0/2.0	
25A7 ...	26.0	14	8146-5-9230	6	2	.90/1.8	(1)
	-	-	- - -	-	8	Rect.	(3)
25AC5 ..	26.0	0	0140-5-0230	5	2	1.0/1.6	
25B5 ...	26.0	0	1465-3-2000	5	2	1.3/2.0	
25B6 ...	26.0	24	0146-5-0230	3	3	1.9/3.7	
25B8 ...	26.0	31	3146-9-82X0	5	2	1.3/2.0	(1)(7)
	-	11	- - -	-	-	1.0/1.5	(3)
25N6 ...	26.0	0	1465-3-2000	5	2	1.3/2.0	
25Y5 ...	26.0	12	1983-4-2000	6	8	Rect.	(1)(3)
26	1.4	9	1450-0-2000	6	1	5.8/9.0	F
27	2.35	20	1450-3-2000	2	2	.63/.97	
27GB5 ..	26.0	11	5531-2-6630 Adapter CL	6	4	5.9/9.0	(6)
29	2.35	10	1453-3-2000	5	2	.52/.80	(1)
	-	-	1435-3-2000	-	-	- / -	(1)
30	2.0	20	1450-0-2000	2	2	.58/.90	F
30AG11	26.0	9	1354-9-X802	5	3	5.1/7.8	(1)(3)
	-	0	0432-0-1890	11	8	Diode	(1)(3)
Adapter CK—Rotate tube so arrow is at pin 6							
31	2.0	47	1450-0-2000	2	2	.65/1.0	F
31AL10	35.0	4	1460-3-5002	6	3	4.6/7.1	(1)
	-	16	1000-3-0002	5	2	1.5/2.4	(1)
Adapter CK—Connect A to Plate Cap; connect B to Grid Cap							
	-	7	-0-0432	-	3	2.5/3.9	(1)
Adapter CK—Connect C to Grid Cap							
GR31 ...	0	0	0009-0-2030	1	6	- / -	*
*Connect 4700Ω 1 watt resistor between Plate Cap and pin 4 on local socket. Increase A to 117—tube will fire. Return A to 0, tube will hold at approx. 25 MA							
31JS6A	35.0	21	0761-0-2365	6	3	2.8/5.6	(6)
Adapter CK—Rotate tube so arrow is at pin 6							
32	2.0	12	1460-0-2000	3	1	.42/.65	F(7)

TUBE TYPE	A	B	ELEMENTS	C	D	REI/AVG	NOTES
32HQ7	35.0	0	4350-6-1020	8	4	9.1/14.0	(1)
			Adapter CK—Rotate tube so arrow is at pin 4				
			0102-4-0300	11	8	Diode	(1)
			Adapter CK—Rotate tube so arrow is at pin 8				
32L7	35.0	8	8146-5-9230	6	3	2.5/5.0	(1)
		0	— — —	11	8	Diode	(3)
33	2.0	32	1450-6-2000	2	2	.90/1.7	F
33GI7	35.0	14	1040-0-3562	6	3	3.2/6.5	(1)
		0	1300-0-0002	11	8	Diode	(1)
			Adapter CK—For second test connect leads from A to Plate Cap				
33GY7	35.0	15	3620-1-9080	6	3	3.2/6.5	(1)
		0	— — —	11	8	Diode	(3)
			Adapter CK—Rotate tube so that arrow is at pin 7 Connect leads from B to Grid Cap; C to Plate Cap.				
34	2.0	11	1460-0-2000	3	1	.40/.62	F (7)
34CE3	35.0	0	1400-3-0042	11	8	Diode	
			Adapter CK				
35	2.5	6	1460-3-2000	3	2	.65/1.0	(7)
36	6.3	16	1460-3-2000	8	2	.55/.85	(7)
37	6.3	7	1450-3-2000	7	2	.59/.90	
38	6.3	10	1460-3-2000	6	1	.57/.87	(7)
38HK7	35.0	13	3620-1-9080	6	3	4.3/8.6	(1)
		0	— — —	11	8	Diode	(3)
40	5.0	7	1450-0-2000	6	1	.1/.15	F
41	6.3	8	1465-3-2000	6	2	.75/1.5	
42	6.3	17	1465-3-2000	2	2	1.3/2.5	
43	26.0	16	1465-3-2000	6	2	1.0/2.0	
45	2.8	45	1450-0-2000	2	2	1.1/2.2	F
45Z3	50.0	13	1403-0-4200	6	8	Rect.	
45Z5	50.0	15	0100-4-0230	6	8	Rect.	
46	2.8	32	1450-4-2000	2	2	1.2/2.4	F
47	2.8	19	1450-6-2000	2	2	1.3/2.5	F
48	35.0	19	1465-3-2000	6	3	1.9/3.8	
49	2.0	0	1456-0-2000	6	1	.43/.66	F
50	7.5	34	1450-0-2000	2	2	.95/1.9	F
50CB	50.0	9	0146-5-0230	6	3	3.5/7.0	
50Z7	50.0	14	0198-4-0230	6	8	Rect.	(1)(3)
52	6.3	0	1450-6-2000	5	3	1.4/2.7	F
53	2.8	48	19X3-5-4200	4	2	2.0/3.1	(1)(2)
53HK7	50.0	13	3620-1-9080	6	3	4.3/8.6	(1)
		0	— — —	11	8	Diode	(3)
55	2.8	19	1400-3-2000	2	2	.71/1.1	(1)(7)
		0	1094-3-2000	11	8	Diode	(1)(2)
56	2.8	6	1450-3-2000	6	2	.71/1.1	
57	2.8	34	1467-3-2000	5	2	.78/1.2	(7)
57AS	6.3	36	1467-3-2000	4	2	.78/1.2	(7)
58	2.8	35	1467-3-2000	5	2	.98/1.5	(7)
64	6.3	6	1460-3-2000	3	2	.71/1.1	(7)
65	6.3	6	1460-3-2000	3	2	.65/1.0	(7)

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
67	6.3	19	1450-3-2000	2	2	.59/.90	
68	6.3	14	1460-3-2000	6	2	.71/1.1	(7)
HY69	6.3	23	1650-7-2000	2	2	1.5/2.9	F (6)
71A	5.0	19	1450-0-2000	6	2	.85/1.7	F
75	6.3	22	1400-3-2000	4	2	.71/1.1	(7)
	-	0	1094-3-2000	11	8	Diode	(1)(2)
76	6.3	6	1450-3-2000	6	2	.78/1.2	
77	6.3	14	1467-3-2000	8	2	.71/1.1	(7)
78	6.3	17	1467-3-2000	5	2	1.0/1.6	(7)
80	5.0	10	1940-0-2000	6	8	Rect.	F (1)(3)
85	6.3	8	1400-3-2000	6	2	.72/1.1	(1)(7)
	-	0	1094-3-2000	11	8	Diode	(1)(2)
88M	6.3	35	0146-0-0230	5	2	1.2/1.9	(7)
117Z4	117.0	14	0100-4-0230	5	8	Rect.	
286A	2.0	35	1467-3-2000	5	2	.78/1.2	(7)
300B	5	42	1450-0-2000	2	3	3.2/4.9	F
310A	10.5	12	1467-3-2000	5	2	1.2/1.8	(7)
311B	10.5	9	1460-3-2000	6	3	1.9/3.0	(7)
352A	10.5	50	1400-3-2000	5	1	3.8/5.9	(7)
	-	0	1049-3-2000	11	8	Diode	(1)(2)
CK544DX	1.25	10	4615-2-0000	9	1	.22/.33	* F
(* No Leakage Test)							
CK556AX	1.25	14	4152-0-0000	5	2	1.0/1.6	F
801	6.3	17	1450-0-2000	2	2	1.2/1.8	F
807	6.3	23	1650-3-2000	2	3	1.6/3.2	(6)
809	6.3	22	1050-0-2000	1	2	.80/1.6	F (6)
812	6.3	7	1050-0-2000	2	2	.80/1.6	F (6)
816	2.8	12	1000-0-2000	6	8	Rect.	F (6)
829B	6.3	5	1563-2-5100	3	4	7.0/14.	(6)
Adapter CG or CM (Connect two plate terminals with jumper)							
832-A	6.3	8	1563-2-5100	3	3	3.5/7.0	(6)
Adapter CG or CM (Connect two plate terminals with jumper)							
840	2.0	9	1657-0-2000	3	1	.26/.40	F (6)
841	7.5	0	1450-0-2000	2	2	.65/1.0	F
842	7.5	38	1450-0-2000	2	2	.65/1.3	F
864	1.25	6	1450-0-2000	6	1	.42/.65	F
866	2.8	12	1000-0-2000	6	8	Rect.	F (6)
874	6.3	0	2040-0-0000	5	6	*	(1)
(* No Leakage Test)							
Increase A to 26.0, firing is indicated by upscale deflection							
885	2.8	40	1450-3-2000	3	7	* Thyatron	
(* Fires from 40-10; cuts off from 10-40)							
950	2.0	13	1450-6-2000	6	1	.62/.95	F
951	2.0	0	1460-0-2000	5	2	.39/.60	F (7)
1006	2.0	32	1940-0-2000	4	8	Rect.	F (1)(2)
1229	2.0	12	1460-0-2000	3	1	.42/.65	F (7)
1609	1.4	5	1450-6-2000	8	1	.47/.72	F

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
-----------	---	---	----------	---	---	---------	-------

1610	2.8	19	1450-6-2000	2	2	1.3/2.5	F
1624	2.8	12	1650-0-2000	2	3	2.0/4.0	F (6)
2093	6.3	12	9412-5-X300	5	3	3.4/5.3	(1)(2)
5693	6.3	16	3751-6-2000	5	3	2.2/3.4	(6)
5634	6.3	12	3751-6-2000	5	3	2.3/3.5	(6)
5635	6.3	11	X510-4-2930	5	3	2.5/3.8	(1)(2)
5646	6.3	11	4315-2-0000	5	2	1.6/2.4	
5656	6.3	9	65X1-2-3943	5	3	3.8/5.8	(1)(2)
5742	4.7	6	1450-0-2000	2	1	.56/.85	F
5784	6.3	13	4612-7-3500	5	3	2.1/3.2	
5812	6.3	27	5711-4-6200	2	3	2.0/4.1	F
5825	1.4	0	1000-0-2000	1	8	Diode	F (6)
5894	6.3	7	1563-2-5100	3	4	6.5/13.	(6)

Adapter CG or CM (Connect two plate terminals with jumper)

5904	26.0	12	5010-3-2040	9	3	3.0/4.7	
5905	26.0	7	5313-4-2630	9	3	1.9/2.9	
5907	26.0	6	5313-4-2630	9	2	2.0/3.0	
5908	26.0	17	5317-4-2630	9	2	1.5/2.2	
5998	6.3	8	543X-9-8120	6	4	7.5/13.	(1)(3)
X-6030	..	3.15	0	0104-4-0200	11	8	Diode	F
6084	6.3	10	5614-2-5634	2	3	2.6/4.1	
CK6213	..	Off	0	2040-2-0000	1	8	Rect.	*

(*No Leakage Test)

6247	6.3	23	5514-3-2040	1	2	1.7/2.6	
6283	6.3	40	1235-4-0000	1	3	3.5/7.0	

Adapter CG or CO

66279	...	6.3	0	0130-3-0230	11	8	Diode	(6)
6360	6.3	27	X352-2-9641	2	2	1.1/1.7	(1)(2)

This set up to be used on tester above serial #5000

6360*	...	6.3	25	5352-2-4641	2	3	2.0/3.1	
-------	-----	-----	----	-------------	---	---	---------	--

* This set up must be used on tester below serial #5000

6524	6.3	34	6X13-2-5600	4	3	2.4/4.5	(6) on l
		-	-	6513-2-X600	-	-	-	(6) on r

This set up must be used on testers above serial #5000

Adapter CG or CM

6524*	...	6.3	4	6513-2-5600	3	4	4.5/9.0	(6)
-------	-----	-----	---	-------------	---	---	---------	-----

* This set up must be used on testers below serial #5000

Adapter CG or CM

(Connect two plate terminals with jumper)

6754	6.3	12	4031-2-0809	6	8	Rect.	(1)(3)
8850	12.6	34	6X13-2-5600	4	3	2.4/4.5	(6) on l
		-	-	6513-2-X600	-	-	-	(6) on r

This set up must be used on testers above serial #5000

Adapter CG or CM

TUBE TYPE	A	B	ELEMENTS	C	D	REJ/AVG	NOTES
-----------	---	---	----------	---	---	---------	-------

6850* ... 12.6 4 6513-2-5600 3 4 4.5/9.0 (6)

*This set up must be used on testers below serial #5000

Adapter CG or CM

(Connect two plate terminals with jumper)

CK6872	6.3	12	4612-7-3500	5	3	2.6/4.1	
6939	6.3	17	53X1-1-4692	5	3	5.3/8.1	(1)(2)
6943	6.3	15	5317-4-2630	5	3	2.3/3.6	
7534/ E130L	6.3	13	0106-5-0230	3	4	8.0/16.	(6)
7643	6.3	12	9561-2-438X	5	3	3.1/4.7	(1)
	-	17	- - -	-	-	3.3/5.0	(3)
7695	50.0	10	6001-2-5304	6	3	4.5/7.0	
7752	6.3	16	5321-4-6700	5	3	2.1/3.2	
7755	6.3	13	5312-4-6300	9	2	1.6/2.5	
7756	6.3	26	3040-8-2510	2	3	2.0/4.0	
7788	6.3	15	3531-2-6476	5	4	16.0/25.0	
7898	12.6	21	9X81-2-4530	4	3	3.6/5.5	(1)(3)
CK7979	1.4	0	1542-0-0000	9	6	10-15 ma	F
7984	12.6	7	1443-5-3352	6	4	6.5/13.	

Adapter CK

CK7994	6.3	10	1545-5-3520	5	4	12./18.	
7995	6.3	9	1352-3-7460	5	4	7.0/11.	
8013A	2.8	15	1000-0-2000	4	8	Rect.	F(1)(6)
	-	-	- - -	-	6	25-47 ma	F(6)

Test #2 Reject below 26 MA

8058 ... 6.3 4 3331-2-0000 5 4 7.8/12. (6) (7)

Grid Cap lead connected to shell at base of tube.

Below serial #3000 use Adapter CI

8106	12.6	19	4361-2-3563	4	4	5.2/8.1	
8113	6.3	15	5312-4-6300	5	3	4.5/7.0	
8136	6.3	0	5312-4-6700	6	4	7.2/11.0	
8233	6.3	27	4761-2-7353	5	4	18.0/26.0	
8393	12.6	2	4531-2-0000	9	4	7.1/11.5	
8608	6.3	31	0761-2-7353	5	4	13.0/20.0	(6)

Adapter CL

THE TRIPLETT ELECTRICAL INSTRUMENT CO.

Bluffton, Ohio

Printed in U.S.A.

Part No. 84-130-061569