

**Technical Note****PROwatt Inverter**

512-0041-01-01 Rev 1

**Sources of TV/Radio  
ElectroMagnetic Interference (EMI)**

The PROwatt inverter uses a 120 kHz switchmode converter to convert low-voltage input power to high-voltage output power. This circuit can produce EMI, which is composed of higher order harmonic frequencies from 120 kHz up to about 20 MHz (with decreasing amplitude). EMI can be conducted along the DC battery lines or picked up by the TV's antenna, resulting in picture noise "lines," or into the radio, resulting in static. A TV's susceptibility to EMI does vary from model to model as TVs have differing abilities to reject/discriminate against EMI noise. EMI is often installation specific, therefore one solution (filter or installation method) may not work effectively in all situations. The two main forms of EMI are as follows:

- a) Transmitted EMI or through the air (inverter to antenna) can be minimized by a distance of at least 6 ft (2 m) between inverter and TV/Radio. Off-air distant stations may be noisier than nearby stations with stronger signals due to the TV/Radio's AGC circuit greatly amplifying a faint signal along with the EMI (electronic noise).
- b) Conducted EMI is when the high frequency noise travels along the DC lines to the DC-powered TV/Radio. In this case you can add a DC EMI filter module to reduce the noise. An inexpensive RF choke in the DC power line going directly to the TV may be sufficient. Such devices are often available at 2-way radio specialty stores for under \$15. A DC EMI filter module costs less than \$50, and should be available locally. One such filter module is available from ICT, part number PCM-12ADL, (604) 888 6304, a 12-amp model which could filter the entire input current of a small inverter (there is also a 25 A and 40 A version) or filter the power line to a small radio, or DC-powered TV.

PROwatt is a trademark of Xantrex International. Xantrex is a registered trademark of Xantrex International. © 2001 Xantrex International. All rights reserved.

Technical Note: *TV/Radio ElectroMagnetic Interference (EMI)- PROwatt* t© 1997 –2002 Xantrex International

UNLESS SPECIFICALLY AGREED TO IN WRITING, XANTREX TECHNOLOGY INC. (“XANTREX”):

(a) MAKES NO WARRANTY AS TO THE ACCURACY, SUFFICIENCY OR SUITABILITY OF ANY TECHNICAL OR OTHER INFORMATION PROVIDED IN ITS MANUALS OR OTHER DOCUMENTATION.

(b) ASSUMES NO RESPONSIBILITY OR LIABILITY FOR LOSS OR DAMAGE, WHETHER DIRECT, INDIRECT, CONSEQUENTIAL OR INCIDENTAL, WHICH MIGHT ARISE OUT OF THE USE OF SUCH INFORMATION. THE USE OF ANY SUCH INFORMATION WILL BE ENTIRELY AT THE USER’S RISK.

Part number: 512-0041-01-01 Rev 1

Contact information:

**Phone:** 1-800-670-0707 (toll-free in North America)

**Phone:** 1-604-422-2777 (direct)

**Fax:** 1-604-420-2145

**Email:** [CustomerService@xantrex.com](mailto:CustomerService@xantrex.com)

**Web:** [www.xantrex.com](http://www.xantrex.com)