

Xantrex™ XW Automatic Generator Start



The Xantrex™ XW Automatic Generator Start (XW AGS) will automatically activate a generator to provide an XW Series Hybrid Inverter/Charger with power to recharge a depleted battery bank or provide additional power for heavy loads. The XW AGS adds intelligence to generator management, thereby eliminating time spent monitoring batteries and inverter loads. It does this by continuously monitoring the battery voltage, state-of-charge, or the inverter charge mode, starting and stopping the generator when the battery needs additional charging. The XW AGS will also start the generator to assist the system's inverter/charger(s) when output power demands are high.

The XW AGS can be customized to suit each user's preferences. The user can define whether the generator should be activated by low-battery voltage, state-of-charge, thermostat operation, or load on the inverter(s). A quiet time setting prevents the generator from starting at inconvenient times. LED lights display the status of the XW AGS, while all user-defined settings are programmed through the XW System Control Panel (XW SCP).

Operational Features

- ▶ Compatibility – the XW AGS connects to other Xanbus™-enabled XW System devices without requiring additional hubs, control cards, or other device-specific control panels
- ▶ Works with AC or DC generators with either two-wire or three-wire start controls
- ▶ Configurability – comprehensive customizable triggers based on low-battery voltage, change in charging state, high inverter load, thermostat signals, planned exercise periods, maximum run time, and quiet-time settings
- ▶ Non-volatile memory – preserves XW AGS settings even if the network power is interrupted or network communication is disrupted

Note: The XW AGS requires an XW System Control Panel (XW SCP) for configuration and monitoring.

Product Features

- ▶ LED display showing at-a-glance status
- ▶ 20-contact generator connector and three built-in relays support 13 preset generator configurations
- ▶ Built-in emergency shutdown
- ▶ Xanbus™-enabled

Interfaces with:

XW Hybrid Inverter/Chargers, XW Solar Charge Controllers, and XW System Control Panel

Xantrex Technology Inc.

Customer Service/Technical Support

customerservice@xantrex.com

Toll free: 1-800-670-0707

www.xantrex.com

Xantrex™ Automatic Generator Start

Electrical Specifications

Nominal input network voltage	15 Vdc
Maximum operating current	200 mA
Communication	Physical layer 2, CAN
Relay contact voltage rating	12 Vdc, 30 Vdc max
Maximum relay contact current	5 Adc
Communication protocol	Xanbus
Maximum cable length	130' (40 m)

Mechanical Specifications

Dimensions (H x W x D)	3.75 x 5.75 x 1.5" (95.5 x 146 x 37 mm)
Weight	0.5 lb (0.225 kg)
Shipping weight	1.70 lb (0.77 kg)
Dimensions (shipping)	10.5 x 8.5 x 2.5" (267 x 216 x 64 mm)
Connectors	Two Xanbus™ RJ45-8 pins One 20-contact pluggable connector (Tyco Mate 'n' Lok two connector) - Wiring harness included
Mounting	Wall mount, 4 x #6 screws included
Standard warranty	Five years
Part number	865-1060

Environmental Specifications

Enclosure type	Indoor
Operating temperature range	-4 to 122°F (-20 to 50°C)
Storage temperature	-40 to 185°F (-40 to 85 °C)

Optional Accessories

Network cables:	
3 feet (0.9 m)	809-0935
5 feet (1.5 m)	809-0936
7 feet (2.0 m)	809-0937
10 feet (3.0 m)	809-0938
14 feet (4.3 m)	809-0939
25 feet (7.6 m)	809-0940
50 feet (15.2 m)	809-0941
75 feet (22.9 m)	809-0942
Network terminators	Male (two per pack): 809-0901 Female (two per pack): 809-0905

Regulatory Approvals

Safety	CSA certified to CSA 107.1-01 and UL 458 4th Ed. including the Marine Supplement
EMC	FCC Part 15B Class B Industry Canada, ICES-0003 Class B

Specifications subject to change without notice.

For more information on the XW System please visit www.xantrex.com/xw