

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
EX		Z-Di	=SM 6T 39A (SMD-Marking)	71a(6x4mm)	SOD-6		=SM 6T....
EX 0022 TA		Z-Di	11.5V	31a		Z-Diode 11V	31a
EX 0048 CE		Z-Di	6.2V	31a		Z-Diode 6.2V	31a
EX 0074 CE		Z-Di	115V	31a		Z-Diode 110V	31a
EXB 919	Fjd	Hybrid-Z-IC	Z-IC, +100V, 0,2A				
EY		Si-N	=2SC2882-Y (SMD-Marking)	39	SOT-89		=2SC2882
EY		Si-N	=2SC3265-Y (SMD-Marking)	35	SOT-23		=2SC3265
EY		Si-N	=2SC3398 (SMD-Marking)	35	SOT-23		=2SC3398
EY		Si-N	=2SC4398 (SMD-Marking)	35(2mm)	SOT-323		=2SC4398
EY		Si-N	=2SD2402-EY (SMD-Marking)	39	SOT-89		=2SD2402
EY		Si-N	=BCW 66RG (SMD-Marking)	35	SOT-23		=BCW 66RG
EY		Si-N	=KTC3265-Y (SMD-Marking)	35	SOT-23		=KTC 3265
EY		Si-N	=KTC4374-Y (SMD-Marking)	39	SOT-89		=KTC 4374
EYV-320(D)		Si-Di	=BA 127	31a		1N4148	31a
EZ		Si-N	=2SD2402-EZ (SMD-Marking)	39	SOT-89		=2SD2402
EZ		Si-N	=BCW 66RH (SMD-Marking)	35	SOT-23		=BCW 66RH
EZ-055....-372	Njr	Z-Di	5...37V, 0,4W	31a	DO-41	Z-DiodeV	31a
							BZX55/...., BZX83/...., ZPD...., 1N5231...58,++
F							
F		Si-N	=2SC4399 (SMD-Marking)	35(2mm)	SOT-323		=2SC4399
F 1		Si-N	=2SC1009-F1 (SMD-Marking)	35	SOT-23		=2SC1009
F 1(p)		Si-N	=BFS 18 (SMD-Marking)	35	SOT-23		=BFS 18
F 1 E23	Shi	MOS-N-FET-e	=2SK1195				
F 1 E50	Shi	MOS-N-FET-e	=2SK1672				
F 1 E90	Shi	MOS-N-FET-e	=2SK1533				
F10		Si-P	=KSA 1182-O (SMD-Marking)	35	SOT-23		=KSA 1182
F1Y		Si-P	=KSA 1182-Y (SMD-Marking)	35	SOT-23		=KSA 1182
F 2		Si-N	=2SC1009-F2 (SMD-Marking)	35	SOT-23		=2SC1009
F 2		Si-N	=2SC2814-F2 (SMD-Marking)	35	SOT-23		=2SC2814
F 2(p)		Si-N	=BFS 19 (SMD-Marking)	35	SOT-23		=BFS 19
F02		N-FET	=SO 4091 (SMD-Marking)	35	SOT-23		=SO 4091
F 3		Si-Di	=1SS193 (SMD-Marking)	35	SOT-23		=1SS193
F 3		Si-N	=2SC1009-F3 (SMD-Marking)	35	SOT-23		=2SC1009
F 3		Si-N	=2SC2814-F3 (SMD-Marking)	35	SOT-23		=2SC2814
F 3		Si-N	=BF 840 (SMD-Marking)	35	SOT-23		=BF 840
F03		N-FET	=SO 4391 (SMD-Marking)	35	SOT-23		=SO 4391
F 3 T		Si-Di	=1PS193 (SMD-Marking)	35	SOT-23		=1PS193
F 3 V50	Shi	MOS-N-FET-e	=2SK1244				
F 3 V90	Shi	MOS-N-FET-e	=2SK1534				
F 3 W90	Shi	MOS-N-FET-e	=2SK1536				
F 4		Si-N	=2SC1009-F4 (SMD-Marking)	35	SOT-23		=2SC1009
F 4		Si-N	=2SC2814-F4 (SMD-Marking)	35	SOT-23		=2SC2814
F 4		Si-N	=BFS 18R (SMD-Marking)	35	SOT-23		=BFS 18R
F 5		Si-Di	=1SS250 (SMD-Marking)	35	SOT-23		=1SS250
F 5		Si-Di	=1SS370 (SMD-Marking)	35(2mm)	SOT-323		=1SS370
F 5		Si-N	=2SC1009-F5 (SMD-Marking)	35	SOT-23		=2SC1009
F 5		Si-N	=2SC2814-F5 (SMD-Marking)	35	SOT-23		=2SC2814
F 5		Si-N	=BFS 19R (SMD-Marking)	35	SOT-23		=BFS 19R
F 05 E23	Shi	MOS-N-FET-e	=2SK1194				
F 5 V50	Shi	MOS-N-FET-e	=2SK1246				
F 5 W50	Shi	MOS-N-FET-e	=2SK1537				
F 6		Si-N	=2SC2223-F6 (SMD-Marking)	35	SOT-23		=2SC2223
F 6 V25	Shi	MOS-N-FET-e	=2SK1391				
F 7		Si-Di	=HSM 83 (SMD-Marking)	35	SOT-23		=HSM 83
F07		N-FET	=SO 4392 (SMD-Marking)	35	SOT-23		=SO 4392
F 7 W90	Shi	MOS-N-FET-e	=2SK1538				
F 8(p)		Si-P	=BF 824 (SMD-Marking)	35	SOT-23		=BF 824
F08		N-FET	=SO 4393 (SMD-Marking)	35	SOT-23		=SO 4393
F 9		Si-Di	=1SS321 (SMD-Marking)	35	SOT-23		=1SS321
F09		N-FET	=SO 3966 (SMD-Marking)	35	SOT-23		=SO 3966
F10		N-FET	=SO 4092 (SMD-Marking)	35	SOT-23		=SO 4092
F 10 V25	Shi	MOS-N-FET-e	=2SK1393				
F 10 W50	Shi	MOS-N-FET-e	=2SK1248				
F 10 W90	Shi	MOS-N-FET-e	=2SK1539				
F 11		N-FET	=SO 4093 (SMD-Marking)	35	SOT-23		=SO 4093
F 12		Si-N	=2SC2223-F12(SMD-Marking)	35	SOT-23		=2SC2223
F 12		Si-N	=2SC4178-F12 (SMD-Marking)	35(2mm)	SOT-323		=2SC4178
F 12		N-FET	=SO 245B (SMD-Marking)	35	SOT-23		=SO 245
F 13		Si-N	=2SC2223-F13(SMD-Marking)	35	SOT-23		=2SC2223
F 13		Si-N	=2SC4178-F13 (SMD-Marking)	35(2mm)	SOT-323		=2SC4178
F 13		N-FET	=BFR 30R (SMD-Marking)	35	SOT-23		=BFR 30R
F 14		N-FET	=BFR 31R (SMD-Marking)	35	SOT-23		=BFR 31R
F 14		Si-N	=2SC2223-F14(SMD-Marking)	35	SOT-23		=2SC2223
F 14		Si-N	=2SC4178-F14 (SMD-Marking)	35(2mm)	SOT-323		=2SC4178
F 14 A...J	Nec	Si-Di	Rr, Uni, 100...1000V, 1A, Uf<1V(1A), A=100, B=200V, C=300, D=400, E=500, F=600, H=800, J=1000V	31a	SOD-57	1N4007	31a
							BY 126...127, BY 133...135, 1N4002...07, ++
F15		N-FET	=SO 5432 (SMD-Marking)	35	SOT-23		=SO 5432
F 15 W50	Shi	MOS-N-FET-e	=2SK1249				
F16		N-FET	=SO 5432R (SMD-Marking)	35	SOT-23		=SO 5432R
F17		N-FET	=SO 5433 (SMD-Marking)	35	SOT-23		=SO 5433
F18		N-FET	=SO 5433R (SMD-Marking)	35	SOT-23		=SO 5433R
F19		N-FET	=SO 5434 (SMD-Marking)	35	SOT-23		=SO 5433R
F20		N-FET	=SO 245BR (SMD-Marking)	35	SOT-23		=SO 245
F 20 W25	Shi	MOS-N-FET-e	=2SK1395				
F 20 W50	Shi	MOS-N-FET-e	=2SK1250				
F21		N-FET	=SO 245A (SMD-Marking)	35	SOT-23		=SO 245
F22		N-FET	=SO 4091R (SMD-Marking)	35	SOT-23		=SO 4091R
F23		N-FET	=SO 4391R (SMD-Marking)	35	SOT-23		=SO 4391R
F24		N-FET	=SO 245AR (SMD-Marking)	35	SOT-23		=SO 245AR
F25		N-FET	=SO 245C (SMD-Marking)	35	SOT-23		=SO 245C
F26		N-FET	=SO 245CR (SMD-Marking)	35	SOT-23		=SO 245CR
F27		N-FET	=SO 4392R (SMD-Marking)	35	SOT-23		=SO 4392R
F28		N-FET	=SO 4393R (SMD-Marking)	35	SOT-23		=SO 4393R

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
F29		N-FET	=SO 3966R (SMD-Marking)	35	SOT-23		=SO 3966R
F 30 S54(DC)	Fch	CMOS-IC	Telecom. μ -Law CODEC, Filter	16-DIC			-
F 30 S57(DC)	Fch	CMOS-IC	Telecom. A-Law CODEC, Filter	16-DIC			-
F 30 S64(DC)	Fch	CMOS-IC	Telecom. μ -Law CODEC, Filter	20-DIC			-
F 30 S67(DC)	Fch	CMOS-IC	Telecom. A-Law CODEC, Filter	20-DIC			-
F30		N-FET	=SO 4092R (SMD-Marking)	35	SOT-23		=SO 4092R
F 30 W25	Shi	MOS-N-FET-e	=2SK1396				
F 31		Si-N	=BF 841 (SMD-Marking)	35	SOT-23		=BF 841
F31		N-FET	=SO 4093R (SMD-Marking)	35	SOT-23		=SO 4093R
F32		N-FET	=SO 5434R (SMD-Marking)	35	SOT-23		=SO 5434R
F 40 W25	Shi	MOS-N-FET-e	=2SK1397				
F 099		Si-Di	=BA 159	31a		BA 159	=BA 159
F 100...117-L	Fer	μ P-IC,MOS-IC	16-Bit μ P System & Peripherie				
F 114 B...F	Nec	Si-Di	FRr, 200...600V, 0.8A, Uf<1.1V(0.8A), <200ns	31a	SOD-57	BYD 33 M	BY 201/... BYV 13...16, RGP 10D...M, ++
F 133		Si-Di	=BY 133	31a		BY 133	=BY 133
F 420		Si-N	=BF 393	7c	TO-92	BF 420 A	=BF 393
F 0810 BH	Tag	50Hz-Thy	200V, 5.1A(Tc=85°C), 8A-, Igt/Ih<25/=75mA	17e	TO-220		TIC 116... BSIC10...M, CS6-..., TAG 660...
F 0810 DH		50Hz-Thy	=F 0810BH: 400V	17e	TO-220		TIC 116... BSIC10...M, CS6-..., TAG 660...
F 0810 MH		50Hz-Thy	=F 0810BH: 600V	17e	TO-220		TIC 116... BSIC10...M, CS6-..., TAG 660...
F 0810 NH		50Hz-Thy	=F 0810BH: 800V	17e	TO-220		TIC 116... BSIC10...M, CS6-..., TAG 660...
F 1612 BH	Tag	50Hz-Thy	200V, 10A(Tc=85°C), 16A-, Igt/Ih=25/100mA	17e	TO-220		T 9.5N... CS15... BSID10...M
F 1612 DH	Tag	50Hz-Thy	=F 1612BH: 400V	17e	TO-220		T 9.5N... CS15... BSID10...M
F 1612 MH		50Hz-Thy	=F 1612BH: 600V	17e	TO-220		T 9.5N... CS15... BSID10...M
F 1612 NH		50Hz-Thy	=F 1612BH: 800V	17e	TO-220		T 9.5N... CS15... BSID10...M
F 2212 DC,PC	Fch	LIN-IC	Telecom. Full Duplex Modem, 2400/1200/600/300 Bps	28-DIC,DIP			-
F 2212 QC		LIN-IC	=F 2212DC,PC: SMD	28-MDIP			-
F 2224 DC,PC	Fch	LIN-IC	Telecom. Full Duplex Modem, 2400/1200/600/300 Bps	28-DIC,DIP			-
F 2224 QC		LIN-IC	=F 2224DC,PC: SMD	28-MDIP			-
F 3054(DC)	Fch	CMOS-IC	Telecom. μ -Law CODEC, Filter	16-DIC			-
F 3057(DC)	Fch	CMOS-IC	Telecom. A-Law CODEC, Filter	16-DIC			-
F 9010...9022		Si-N/P	=CS 9010...9022	7	TO-92	=CS 9010...22	
F 40098 BPC	Fch	CMOS-Logic	6x invert. Treiber/Driver, Tri-State	16-DIP			U 40098, V 40098BPC
FA		MOS-P/N-FETe	= μ PA505T (SMD-Marking)	45	SOT-153		= μ PA505T
FA		Si-N	=2SC2619-A (SMD-Marking)	35	SOT-23		=2SC2619
FA		Si-N	=BFP 81 (SMD-Marking)	44	SOT-143		=BFP 81
FA		Si-N	=BFQ 17 (SMD-Marking)	39	SOT-89		=BFQ 17
FA		Si-N	=BSV 65A (SMD-Marking)	35	SOT-23		=BSV 65A
FA		Si-P	=HQ 2A4A (SMD-Marking)	39	SOT-89		=HQ 2...
FA 1 A3Q	Nec	Si-N+R	=AA 1A3Q: SMD	(FN1A3Q) 35a	SOT-23		DTC 1132K, UN 2219
FA 1 A4M	Nec	Si-N+R	=AA 1A4M: SMD	(FN1A4M) 35a	SOT-23		DTC 113EK, RN 1402, UN 2211, 2SC3398,++
FA 1 A4P	Nec	Si-N+R	=AA 1A4P: SMD	(FN1A4P) 35a	SOT-23		DTC 114YK, RN 1407, UN 2214, 2SC4047,++
FA 1 A4Z	Nec	Si-N+R	=AA 1A4Z: SMD	(FN1A4P) 35a	SOT-23		DTC 114TK, RN 1411, UN 2215, 2SC3859,++
FA 1 F4M	Nec	Si-N+R	=AA 1F4M: SMD	(FN1F4M) 35a	SOT-23		DTC 124EK, RN 1403, UN 2212, 2SC3396,++
FA 1 F4N	Nec	Si-N+R	=AA 1F4N: SMD	(FN1F4N) 35a	SOT-23		BCR 142, DTC 124XK, KSR 1107, RN 1408
FA 1 F4Z	Nec	Si-N+R	=AA 1F4Z: SMD	(FN1F4Z) 35a	SOT-23		DTC 124TK, KSR 1111, UN 2217, 2SC4120
FA 1 L3M	Nec	Si-N+R	=AA 1L3M: SMD	(FN1L3M) 35a	SOT-23		DTC 143EK, RN 1401, UN 221L, 2SC4362,++
FA 1 L3N	Nec	Si-N+R	=AA 1L3N: SMD	(FN1L3N) 35a	SOT-23		DTC 143XK, KSR 1105, UN 221F, 2SC4360
FA 1 L3Z	Nec	Si-N+R	=AA 1L3Z: SMD	(FN1L3Z) 35a	SOT-23		DTC 143TK, RN 1410, UN 2216, 2SC3900,++
FA 1 L4L	Nec	Si-N+R	=AA 1L4L: SMD	(FN1L4L) 35a	SOT-23		DTC 144WK, RN 1409, UN 221E, 2SC3397,++
FA 1 L4M	Nec	Si-N+R	=AA 1L4M: SMD	(FN1L4M) 35a	SOT-23		DTC 144EK, RN 1404, UN 2213, 2SC3395,++
FA 1 L4Z	Nec	Si-N+R	=AA 1L4Z: SMD	(FN1L4Z) 35a	SOT-23		DTC 144TK, KSR 1112, UN 2210, 2SC3898
FA 3		Si-N	=2SC4179-FA3 (SMD-Marking)	35(2mm)	SOT-323		=2SC4179
FA 3 L4Z	Nec	Si-N+R	=BA 3L4Z: SMD	(FN3L4Z) 35a	SOT-23		-
FA 4		Si-N	=2SC4179-FA4 (SMD-Marking)	35(2mm)	SOT-323		=2SC4179
FA 8025	Hit	Hybrid-Z-IC	Z-IC, +14.2...14.8V, 3.5A				-
FB		Si-N	=2SC2619-B (SMD-Marking)	35	SOT-23		=2SC2619
FB		Si-N	=2SC3053-B (SMD-Marking)	35	SOT-23		=2SC3053
FB		Si-N	=2SC4258-B (SMD-Marking)	35(2mm)	SOT-323		=2SC4258
FB		Si-N	=2SC5016 (SMD-Marking)	=35	(T Mini)		=2SC5016
FB		Si-N	=BFP 17 (SMD-Marking)	44	SOT-143		=BFP 17
FB		Si-N	=BFQ 19 (SMD-Marking)	39	SOT-89		=BFQ 19
FB		Si-N	=BSV 65B (SMD-Marking)	35	SOT-23		=BSV 65B
FB 1 A3M...L3N	Nec	Si-N+R	=AB 1A3M...L3N: SMD	(FP1... 35a)	SOT-23		-
FB 2060A,B	Fch	Si-N	=2N2060A,B:	TO-71	(EBC-EBC-)		=2N2060A,B
FB 3423	Fch	Si-N	=2N3423:	TO-71	(EBC-EBC-)		=2N3423
FB 3424	Fch	Si-N	=2N3424:	TO-71	(EBC-EBC-)		=2N3424
FB 3726	Fch	Si-P	=2N3726:	TO-71	(EBC-EBC-)		=2N3726
FB 3727	Fch	Si-P	=2N3727:	TO-71	(EBC-EBC-)		=2N3727
FB 3728	Fch	Si-N	=2N3728:	TO-71	(EBC-EBC-)		=2N3728
FB 3729	Fch	Si-N	=2N3729:	TO-71	(EBC-EBC-)		=2N3729
FB 4015	Fch	Si-P	=2N4015:	TO-71	(EBC-EBC-)		=2N4015
FB 4016	Fch	Si-P	=2N4016:	TO-71	(EBC-EBC-)		=2N4016
FBC 737		Si-N	=BC 737			BC 337	=BC 737
FBC 738		Si-N	=BC 738			BC 337	=BC 738
FC		Si-N	=2SC2619-C (SMD-Marking)	35	SOT-23		=2SC2619
FC		Si-N	=2SC3053-C (SMD-Marking)	35	SOT-23		=2SC3053
FC		Si-N	=2SC3438-C (SMD-Marking)	39	SOT-89		=2SC3438
FC		Si-N	=2SC4258-C (SMD-Marking)	35(2mm)	SOT-323		=2SC4258
FC		Si-N	=BFP 29 (SMD-Marking)	44	SOT-143		=BFP 29
FC		Si-N	=BFQ 64(SMD-Marking)	39	SOT-89		=BFQ 64
FC 11	Say	N-FET	SMD, Dual, =2x 2SK772, Δ Ugs<30mV	45	SOT-153		-
FC 101	Say	Si-P	SMD, Dual, =2x 2SA1622	46	SOT-163		-
FC 102	Say	Si-N	SMD, Dual, =2x 2SC4211	46	SOT-163		-
FC 103	Say	Si-P	SMD, Dual, =2x 2SA1622	45	SOT-153		-
FC 104	Say	Si-N	SMD, Dual, =2x 2SC4211	45	SOT-153		-
FC 105	Say	Si-P	SMD, Dual, =2x 2SA1341	46	SOT-163		-
FC 106	Say	Si-N	SMD, Dual, =2x 2SC3395	46	SOT-163		-
FC 107	Say	Si-P	SMD, Dual, =2x 2SA1341	45	SOT-153		-
FC 108	Say	Si-N	SMD, Dual, =2x 2SC3395	45	SOT-153		-
FC 109	Say	Si-P	SMD, Dual, =2x 2SA1342	46	SOT-163		-
FC 110	Say	Si-N	SMD, Dual, =2x 2SC3396	46	SOT-163		-

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International	
FC 111	Say	Si-P	SMD, Dual, =2x 2SA1342	45	SOT-153	-	-	
FC 112	Say	Si-N	SMD, Dual, =2x 2SC3396	45	SOT-153	-	-	
FC 113	Say	Si-P	SMD, Dual, =2x 2SA1344	46	SOT-163	-	-	
FC 114	Say	Si-N	SMD, Dual, =2x 2SC3398	46	SOT-163	-	-	
FC 115	Say	Si-P	SMD, Dual, =2x 2SA1344	45	SOT-153	-	-	
FC 116	Say	Si-N	SMD, Dual, =2x 2SC3398	45	SOT-153	-	-	
FC 117	Say	Si-P	SMD, Dual, =2x 2SA1745	46	SOT-163	-	-	
FC 118	Say	Si-N	SMD, Dual, =2x 2SC4555	46	SOT-163	-	-	
FC 119	Say	Si-N	SMD, Dual, =2x 2SC2814	46	SOT-163	-	-	
FC 120	Say	Si-N	SMD, Dual, =2x 2SC3142	46	SOT-163	-	-	
FC 121	Say	Si-P	SMD, Dual, =2x 2SA1502	45	SOT-153	-	-	
FCB 61 C65(LLL)P	Phi		CMOS-sRAM-IC8k x 8Bit, 55ns, 0...70°	28-DIP				
FCB 61 C65(LLL)T	Phi		CMOS-sRAM-IC=FCB 61...P: SMD	28-MDIP				
FCF 61 C65(LLL)T	Phi		CMOS-sRAM-IC=FCB 61...: SMD, -40...+85°	28-MDIP				
FCM 7010		MOS-IC	Digital-Uhr/Digital Clock	40-DIL				
FCS 6208...6209		Si-N/P	=CS 6208...6209	7	TO-92	=CS 6208...09		
FCS 9010...9022		Si-N/P	=CS 9010...9022	7	TO-92	=CS 9010...22		
FD		Si-N	=2SC3053-D (SMD-Marking)	35	SOT-23		=2SC3053	
FD		Si-N	=2SC3438-D (SMD-Marking)	39	SOT-89		=2SC3438	
FD		Si-N	=2SC4258-D (SMD-Marking)	35(2mm)	SOT-323		=2SC4258	
FD		Si-P	=BCV 26 (SMD-Marking)	35	SOT-23		=BCV 26	
FD		Si-N	=BFP 35A (SMD-Marking)	44	SOT-143		=BFP 35A	
FD		Si-N	=BFQ 17P (SMD-Marking)	39	SOT-89		=BFQ 17P	
FD 100	Fch	Si-Di	SS, 75V, Uf<1V(10mA), <4ns	31a	DO-7	1N4148	31a	BAW 62, BAW 76, BAX 95, 1N4148...49, ++
FD 111	Fch	Si-Di	SS, 75V, Uf<1V(10mA), <5ns	31a	DO-7	1N4148	31a	BAW 62, BAW 76, BAX 95, 1N4148...49, ++
FD 200	Fch	Si-Di	S, 200V, Uf<1V(0.1A), <50ns	31a	DO-7			BA 197...198, BAV 20...21, BAW 50
FD 222	Fch	Si-Di	S, 150V, Uf<1,05V(0.1A), <60ns	31a	DO-7			BA 196...198, BAV 16, BAV 20...21, BAW 50
FD 300	Fch	Si-Di	Uni, 150, Uf<1V(0.2A), Ir<1nA(125V)	31a	DO-7			BAS 45, FDH 300, FDH 333
FD 333	Fch	Si-Di	Uni, 150, Uf<1V(0.2A), Ir<3nA(125V)	31a	DO-7			BAS 45, FDH 300, FDH 333
FD 600	Fch	Si-Di	SS, 75V, Uf<1V(0.2A), <4ns	31a	DO-7			BAV 12, BAV 14, BAW 26...27, BAX 81
FD 700	Fch	Si-Di	SS, 20V, 0.05A, Uf=0.89...1.1V(0.05A), <0.7ns	31a	DO-7			FDH 700
FD 777	Fch	Si-Di	SS, 8V, 0.05A, Uf=0.89...1.35V(0.05A), <0.75ns	31a	DO-7			FDH 777
FD 6666	Fch	Si-Di	SS, 75V, Uf<1V(0.2A), <5ns	31a	DO-7			BAW 26...27, BAV 12, BAV 14, BAX 81
FDH 300	Fch, Nsc	Si-Di	Uni, 125V, 0.2A, Uf<1V(0.2A), Ir<1nA(125V)	31a	DO-35			BAS 45, BAY 135
FDH 333	Fch, Nsc	Si-Di	Uni, 125V, 0.2A, Uf<1.05V(0.2A), Ir<3nA(125V)	31a	DO-35			BAS 45, BAY 135
FDH 400	Fch, Nsc	Si-Di	Uni, S, 175V, 0.2A, Uf<1V(0.2A), <50ns	31a	DO-35	BA 159	31a	BA 197...198, BAV 20...21, BAW 50
FDH 444	Fch, Nsc	Si-Di	Uni, S, 125V, 0.2A, Uf<1V(0.2A), <60ns	31a	DO-35	BA 159	31a	BA 196...198, BAV 15...16, BAV 19...21
FDH 600	Fch, Nsc	Si-Di	SS, 50V, 0.2A, Uf<0.92V(0.1A), <4ns	31a	DO-35	1N4148	31a	BAW 62, BAW 76, BAX 95, 1N4148...49, ++
FDH 666	Fch, Nsc	Si-Di	SS, 25V, 0.2A, Uf<1V(0.1A), <4ns	31a	DO-35	1N4148	31a	BAW 62, BAW 76, BAX 95, 1N4148...49, ++
FDH 700	Fch	Si-Di	SS, 20V, 0.05A, Uf<1.10V(0.05A), <0.7ns	31a	DO-7			FD 700
FDH 777	Fch	Si-Di	SS, 8V, 0.05A, Uf<1.35V(0.05A), <0.75ns	31a	DO-7			FD 777
FDH 900	Fch, Nsc	Si-Di	SS, 40V, 0.2A, Uf<1V(0.1A), <4ns	31a	DO-35	1N4148	31a	BAV 10, BAW 24...27, BAX 81, 1N4150, ++
FDH 999	Fch, Nsc	Si-Di	SS, 25V, 0.2A, Uf<1V(0.01A), <5ns	31a	DO-35	1N4148	31a	BAV 10, BAW 24...27, BAX 81, 1N4150, ++
FDH 1000	Fch, Nsc	Si-Di	S, 50V, 0.2A, Uf<1V(0.5A)	31a	DO-35			BAW 24...27, BAX 82, BAY 95, 1N4151
FDN 600	Fch	Si-Di	=FDH 600:	31a	DO-34			=FDH 600
FDN 666	Fch	Si-Di	=FDH 666:	31a	DO-34			=FDH 666
FDR 300	Fch	Si-Di	S, RadH, 250V, Uf<0.85V(0.1A), <325ns	31a	DO-7			-
FDR 600	Fch	Si-Di	SS, RadH, 75V, Uf<1V(0.2A), <4ns	31a	DO-7			-
FDR 700	Fch	Si-Di	SS, RadH, 30V, Uf<1.1V(0.05A), <0.7ns	31a	DO-7			-
FE		Si-N	=2SC3438-E (SMD-Marking)	39	SOT-89			=2SC3438
FE(p.s)		Si-P	=BCV 46 (SMD-Marking)	35	SOT-23			=BCV 46
FE		Si-N	=BFP 93A (SMD-Marking)	44	SOT-143			=BFP 93A
FE		Si-N	=BFQ 19P (SMD-Marking)	39	SOT-89			=BFQ 19P
FE 1 A...H	Gie	Si-Di	FRr, 50...400V, 1A, Uf<0.95V(1A), <30ns A=50, B=100, C=150, D=200, E=250, F=300, G=350, H=400V	31a	SOD-57	BYV 27/200	31a	BYV 26B...E, EGP 10A...G
FE 2 A...H	Gie	Si-Di	FRr, 50...400V, 2A, Uf<0.95V(2A), <35ns	31a	SOD-57	BYV 27/200	31a	BYD 47A...G, BYV 27/..., EGP 20A...G
FE 3 A...H	Gie	Si-Di	FRr, 50...400V, 3A, Uf<0.95V(3A), <35ns	31a	SOD-64	BYV 28/200	31a	BYV 28/..., EGP 30A...G
FE 5 A...D	Gie	Si-Di	FRr, 50...200V, 5A, Uf<0.95(5A), <35ns	31a	SOD-64			BYV 61...63, EGP 50A...G
FE 6 A...H	Gie	Si-Di	FRr, 50...400V, 6A, Uf<0.95V(6A), <35ns	31a	SOD-64			BYV 61...63
FE 8 A...J	Gie,Tho	Si-Di	P FRr, 50...600V, 8A(Tc=100°), Uf<0.95V(8A), <35ns A=50, B=100, C=150, D=200, F=300, G=400, H=500, J=600V	17k	TO-220			BYT 79/..., BYV 29/..., BYR 29/..., ++
FE 16 A...J	Gie,Tho	Si-Di	Dual, 50...600V(Tc=100°), 16A, Uf<0.95V(8A), <35ns	17e	TO-220			BYV 34/...
FE 16 AD...JD		Si-Di	=FE 16A...J:	17r	TO-220			FED 16AT...JT
FE 16 AN...JN		Si-Di	=FE 16A...J:	17h	TO-220			FEN 16AT...JT
FE 30 A...J	Gie,Tho	Si-Di	Dual, 50...600V, 30A(Tc100°), Uf<0.95V(30A), <35...50ns	23f	TO-3			BYV 72/..., BYV 74/..., MUR 3005...3060PT
FE 30 AD...JD		Si-Di	=FE 30A...J:	23s	TO-3			-
FE 30 AN...JN		Si-Di	=FE 30A...J:	23n	TO-3			-
FE 0654A...C	Fch, Tsc	N-FET	HF/S25V, Idss=1...40mA, Up<8V	8b	TO-106			BF 244A...C, BF 245A...C, 2N5163
FE 0655A...C	Fch, Tsc	N-FET	Uni, 30V, Idss>3mA, Up<10V	8b	TO-106			BFS 74...79, BSV 78...80, 2N4856...4861
FE 1718A...E	Fch	Si-P	SMD, Dual, 40V, >400MHz	10-MDIP	TO-89			-
FE 2060A.B	Fch	Si-N	=2N2060A.B: SMD	10-MDIP	TO-89			-
FE 2223(A)	Fch	Si-N	=2N2223(A): SMD	10-MDIP	TO-89			-
FE 2913...2920(A)	Fch	Si-N	=2N2913...2920(A): SMD	10-MDIP	TO-89			-
FE 3423	Fch	Si-N	=2N3423: SMD	10-MDIP	TO-89			-
FE 3424	Fch	Si-N	=2N3424: SMD	10-MDIP	TO-89			-
FE 3726	Fch	Si-P	=2N3726: SMD	10-MDIP	TO-89			-
FE 3727	Fch	Si-P	=2N3727: SMD	10-MDIP	TO-89			-
FE 3728	Fch	Si-N	=2N3728: SMD	10-MDIP	TO-89			-
FE 3729	Fch	Si-N	=2N3729: SMD	10-MDIP	TO-89			-
FE 3819	Fch, Tsc	N-FET	=2N3819: 0.3W	8b	TO-106			=2N3819
FE 4015...4025	Fch	Si-P	=2N4015...4025: SMD	10-MDIP	TO-89			-
FE 4302...4304	Fch, Tsc	N-FET	=2N4302...4304: 0.3W	8b	TO-106			=2N4302...4303
FE 5245...5247	Fch, Tsc	N-FET	=2N5245...5247: 0.36W	8f	TO-106			=2N5245...5247
FE 5257...5259	Fch, Tsc	N-FET	=2N5257...5259: 0.31W	8b	TO-106			=2N5257...5259
FE 5284...5286	Fch, Tsc	N-FET	=2N5284...5286: 0.31W	8f	TO-106			=2N5284...5286
FED 16 AT...JT	Gie	Si-Di	=FEP 16AT...JT:	17r	TO-220			FE 16AD...JD
FED 30 AP...JP	Gie	Si-Di	=FEP 30AP...JP:	18r	TO-247			-
FEN 16 AT...JT	Gie	Si-Di	=FEP 16AT...JT:	17h	TO-220			FE 16AN...JN
FEN 30 AP...JP	Gie	Si-Di	=FEP 30AP...JP:	18h	TO-247			-
FEP 16 AT...JT	Gie	Si-Di	Dual, 50...600V, 16ATc=100°, Uf<0.95V(8A), <50ns A=50, B=100, C=150, D=200, F=300, G=400, H=500, J=600V	17e	TO-220			BYV 34/..., FE 16A...J

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International	
FEP 30 AT...JT	Gie	Si-Di	Dual, 50...600V, 30A(Tc=100°), Uf<0,95V(15A), <50ns	18e			BYV 74/..., MUR 3005PT...3060PT	
FER 8 AT...JT	Gie	Si-Di	=FES 8AT...JT:	17m			-	
FER 16 AT...JT	Gie	Si-Di	=FES 16AT...JT:	17m			-	
FES 8 AT...JT	Gie	Si-Di	P FRr, 50...600V, 8A(Tc=100°), Uf<0,95V(8A), <35ns A=50,B=100,C=150,D=200,F=300,G=400,H=500,J=600V	17k			BYR 29/..., BYT 86/..., FE 8A...J	
FES 16 AT...JT	Gie	Si-Di	FRr, 50...600V, 16A(Tc=100°), Uf<0,98V(16A), <35ns	17k			BYR 79/..., BYT 87/..., FE 16A...J	
FF(p,s)		Si-N	=BCV 27 (SMD-Marking)	35			-BCV 27	
FF		Si-N	=BFQ 18A (SMD-Marking)	39			-BFQ 18A	
FG(p,s)		Si-N	=BCV 47 (SMD-Marking)	35			-BCV 47	
FG		Si-N	=BFQ 149 (SMD-Marking)	39			-BFQ 149	
FG		Si-N	=BFQ 19S (SMD-Marking)	39			-BFQ 19S	
FG 1		Ge-P	=2SB33		AC 151	2a	-2SB33	
FG 2 N	Fdj	Si-Di	TV Damper-Di, 300V, 1A, Uf<1,1V(2A)	31a	(6x9mmØ)	BYD 33 M	31a	BY 201/3, BYX 55/350, MR 813, RGP 10G,++
FH(s)		Si-N	=BFN 24 (SMD-Marking)	35			-BFN 24	
FHP		Si-N	=2SC5020-P (SMD-Marking)	35(2mm)			-2SC5020	
FHQ		Si-N	=2SC5020-Q (SMD-Marking)	35(2mm)			-2SC5020	
FHR		Si-N	=2SC5020-R (SMD-Marking)	35(2mm)			-2SC5020	
FI		MOS-N-FET-d	=3SK186 (SMD-Marking)	44			-3SK186	
FI		MOS-N-FET-d	=3SK217 (SMD-Marking)	44			-3SK217	
FJ		N-FET	=2SK1069 (SMD-Marking)	35(2mm)			-2SK1069	
FJ(s)		Si-N	=BFN 26 (SMD-Marking)	35			-BFN 26	
FJ 3		N-FET	=2SK771-3 (SMD-Marking)	35			-2SK771	
FJ 4		N-FET	=2SK771-4 (SMD-Marking)	35			-2SK771	
FJ 5		N-FET	=2SK771-5 (SMD-Marking)	35			-2SK771	
FJ 2501		Si-P-Darl	=BDX 34A	17j		BD 902	17j	-BDX 34(A...D)
FJ 3001		Si-N-Darl	=BDX 33A	17j		BD 901	17j	-BDX 33(A...D)
FK		Si-P	=2SB800-FK (SMD-Marking)	39			-2SB800	
FK(s)		Si-P	=BFN 25 (SMD-Marking)	35			-BFN 25	
FKE 4 F2/...	Skr	Si-Di	=SKE 4F2/...	33a		SKE 4F2/10	33a	-
FL		Si-P	=2SA1434 (SMD-Marking)	35			-2SA1434	
FL		Si-P	=2SB800-FL (SMD-Marking)	39			-2SB800	
FL(s)		Si-P	=BFN 27 (SMD-Marking)	35			-BFN 27	
FLV....		Opto						
FM		Si-P	=2SB800-FM (SMD-Marking)	39			-2SB800	
FM		Si-Di	=BB 804 (SMD-Marking)	35			-BB 804	
FMA 1	Rhm	Si-P+R	SMD, Dual, Rb=Rbe=22kΩ, 50V, 30mA	45			-	
FMA 2	Rhm	Si-P+R	SMD, Dual, Rb=Rbe=47kΩ, 50V, 30mA	45			-	
FMA 3	Rhm	Si-P+R	SMD, Dual, Rb=4,7kΩ, Rbe=-, 50/50V, 100mA	45			-	
FMA 4	Rhm	Si-P+R	SMD, Dual, Rb=10kΩ, Rbe=-, 50/50V, 100mA	45			-	
FMA 5	Rhm	Si-P+R	SMD, Dual, Rb=2,2k, Rbe=47kΩ, 50V, 100mA	45			-	
FMA 6	Rhm	Si-P+R	SMD, Dual, Rb=47kΩ, Rbe=-, 50/50V, 100mA	45			-	
FMC 1	Rhm	Si-N/P	SMD, NPN+PNP, Rb=4,7kΩ, Rbe=-, 50/50V, 100mA	45			-	
FMC 2	Rhm	Si-N/P	SMD, NPN+PNP, Rb=Rbe=22kΩ, 50V, 100mA	45			-	
FMC 3	Rhm	Si-N/P	SMD, NPN+PNP, Rb=Rbe=10kΩ, 50V, 50mA	45			-	
FMG 1	Rhm	Si-N+R	SMD, Dual, Rb=Rbe=22kΩ, 50V, 30mA	45			-	
FMG 2	Rhm	Si-N+R	SMD, Dual, Rb=Rbe=22kΩ, 50V, 30mA	45			-	
FMG 3	Rhm	Si-N+R	SMD, Dual, Rb=4,7kΩ, Rbe=-, 50/50V, 100mA	45			-	
FMG 4	Rhm	Si-N+R	SMD, Dual, Rb=10kΩ, Rbe=-, 50/50V, 100mA	45			-	
FMG 5	Rhm	Si-N+R	SMD, Dual, Rb=10k, Rbe=47kΩ, 50V, 100mA	45			-	
FMG 6	Rhm	Si-N+R	SMD, Dual, Rb=47kΩ, Rbe=-, 50/50V, 100mA	45			-	
FMG 7	Rhm	Si-N+R	SMD, Dual, Rb=10kΩ, Rbe=-, 50/50V, 100mA	45			-	
FMG 8	Rhm	Si-N+R	SMD, Dual, Rb=4,7k, Rbe=47kΩ, 50V, 100mA	45			-	
FMMT 918	Fer	Si-N	=2N918: SMD	35a			BF 517, BFS 17, 2SC3016, 2SC3061, ++	
FMMT 2222(A)	Fer	Si-N	=2N2222(A): SMD	35a			BSR14, BSS79, PMBT2222(A), SMBT2222(A)	
FMMT 2222(A)R	Fer	Si-N	=2N2222(A): SMD	35d			-	
FMMT 2369(A)	Fer	Si-N	=2N2369(A): SMD	35a			2SC4168, PMBT 2369(A)	
FMMT 2484	Fer	Si-N	=2N2484: SMD	35a		BC 850	35a	BC 850, 2SC3323
FMMT 2907(A)	Fer	Si-P	=2N2907(A): SMD	35a			BSR15...16,BSS80,PMBT2907(A),SMBT2907(A)	
FMMT 2907(A)R	Fer	Si-P	=2N2907(A): SMD	35d			-	
FMMT 3903...3904	Fer	Si-N	=2N3903...3904: SMD	35a		BC 846	35a	BC846, BCV71...72, PMBT3903..., SMBT3904
FMMT 3905...3906	Fer	Si-P	=2N3905...3906: SMD	35a		BC 856	35a	BC856...857, BCX71, PMBT3905..., SMBT3906
FMMT 4124	Fer	Si-N	=2N4124: SMD	35a		BC 846	35a	BC 846...848, BSR 17, SMBT 4124, 2SC3392
FMMT 4125	Fer	Si-P	=2N4125: SMD	35a		BC 856	35a	BC 856...858, BSR 18, SMBT 2126, 2SA1607
FMMT 5087	Fer	Si-P	=2N5087: SMD	35a		BC 860	35a	BC 860, BCF 70, SMBT 5087, 2SA1311
FMMT 5087 R	Fer	Si-P	=2N5087: SMD	35a				-
FMMT-A05...06	Fer	Si-N	=MPS-A05...06: SMD	35a				BCW 65...66, PMBT-A05...06, SMBTA 05...06++
FMMT-A12...14	Fer	Si-N-Darl	=MPS-A12...14: SMD	35a				BCV 27, PMBT-A12...14, SMBTA 13...14++
FMMT-A20	Fer	Si-N	=MPS-A20: SMD	35a		BC 846	35a	BC 846...847, BCW 71...72, SMBTA 20, ++
FMMT-A42...43	Fer	Si-N	=MPS-A42...43: SMD	35a				PMBT-A42...43, SMBTA 42...43
FMMT-A42R...43R	Fer	Si-N	=MPS-A42...43: SMD	35d				-
FMMT-A55...56	Fer	Si-P	=MPS-A55...56: SMD	35a				BCW 68, BCX 42, PMBT-A55..., SMBTA 55...++
FMMT-A70	Fer	Si-P	=MPS-A50: SMD	35a		BC 856	35a	BC 856...857, BCW 69...70, 2SA1311, ++
FMMT-A92...93	Fer	Si-P	=MPS-A92...93: SMD	35a				PMBT-A92...93, SMBTA 92...93
FMMT-A92R...93R	Fer	Si-P	=MPS-A92...93: SMD	35d				-
FMP 18 N05	Fch	MOS-N-FET-e	VFET, 50/30V, 18/50A, 75W, on<0,1Ω(10A)	17p				BUZ 21...22, IRF 540...43, 2SK674, 2SK1417
FMP 20 N05	Fch	MOS-N-FET-e	VFET, 50/30V, 20/60A, 75W, <85mΩ(10A), <140/135ns	17p				BUZ 21...22, IRF 540...43, 2SK674, 2SK1417
FMP 30 N05	Fch	MOS-N-FET-e	VFET, 50/30V, 30A, 100W, on<0,05Ω	17p				BUK 555/50, BUZ 11...12, PRFZ 42, 2SK856+
FMP 35 N05	Fch	MOS-N-FET-e	VFET, 50/30V, 35A, 100W, on<0,04Ω	17p				BUK 555/50, BUZ 11...12, PRFZ 42, 2SK856+
FMPS-A 05	Fch	Si-N	=MPS-A05	7e		-MPS-A05		-MPS-A05
FMPS-A 06	Fch	Si-N	=MPS-A06	7e		-MPS-A06		-MPS-A06
FMPS-A 55	Fch	Si-P	=MPS-A55	7e		-MPS-A55		-MPS-A55
FMPS-A 56	Fch	Si-P	=MPS-A56	7e		-MPS-A56		-MPS-A56
FMS 1	Rhm	Si-P	SMD, Dual, Uni, 50/40V, 100mA	45				-
FMS 2	Rhm	Si-P	SMD, Dual, Uni, 50/40V, 100mA	45				-
FMS 3	Rhm	Si-P	SMD, Dual, Uni, 120/120V, 50mA	45				-
FMS 4	Rhm	Si-P	SMD, Dual, Uni, 120/120V, 50mA	45				-
FMW 1	Rhm	Si-N	SMD, Dual, Uni, 50/40V, 100mA	45				-
FMW 2	Rhm	Si-N	SMD, Dual, Uni, 50/40V, 100mA	45				-
FMW 3	Rhm	Si-N	SMD, Dual, Uni, 120/120V, 50mA	45				-
FMW 4	Rhm	Si-N	SMD, Dual, Uni, 120/120V, 50mA	45				-
FMW 5	Rhm	Si-N	SMD, Dual, Uni, 50/40V, 100mA	45				-
FMW 6	Rhm	Si-N	SMD, Dual, HF, 30/18V, 50mA, >600MHz	45				-

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
FMW 7	Rhm	Si-N	SMD, Dual, HF, 20/11V, 50mA, >1400MHz	45	SOT-153	-	-
FMW 8	Rhm	Si-N	SMD, Dual, HF, 20/11V, 50mA, >1400MHz	45	SOT-153	-	-
FMW 9	Rhm	Si-N	SMD, Dual, HF, 20/11V, 50mA, >1400MHz	45	SOT-153	-	-
FMW 10	Rhm	Si-N	SMD, Dual, HF, 30/18V, 50mA, >600MHz	45	SOT-153	-	-
FMY 1	Rhm	Si-P/N	SMD, PNP+NPN, 50/40V, 100mA, 140MHz	45	SOT-153	-	-
FMY 3	Rhm	Si-P/N	SMD, PNP+NPN, 50/40V, 100mA, 140MHz	45	SOT-153	-	-
FMY 4	Rhm	Si-P/N	SMD, PNP+NPN, 50/40V, 100mA, 140MHz	45	SOT-153	-	-
FMY 5	Rhm	Si-P/N	SMD, PNP+NPN, 120/120V, 50mA, 140MHz	45	SOT-153	-	-
FN...FS							
FN 1 A3Q	Nec	Si-P+R	=AN 1A3Q: SMD	IFA1A3Q 35a	SOT-23	-	DTA 113ZK, UN 2119
FN 1 A4M	Nec	Si-P+R	=AN 1A4M: SMD	IFA1A4M 35a	SOT-23	-	DTA 114EK, RN 2402, UN 2111, 2SA1344,++
FN 1 A4P	Nec	Si-P+R	=AN 1A4P: SMD	IFA1A4P 35a	SOT-23	-	DTA 114YK, RN 2407, UN 2114, 2SA1563,++
FN 1 A4Z	Nec	Si-P+R	=AN 1A4Z: SMD	IFA1A4Z 35a	SOT-23	-	DTA 114TK, RN 2411, UN 2115, 2SA1496,++
FN 1 F4M	Nec	Si-P+R	=AN 1F4M: SMD	IFA1F4M 35a	SOT-23	-	DTA 124EK, RN 2403, UN 2112, 2SA1342,++
FN 1 F4N	Nec	Si-P+R	=AN 1F4N: SMD	IFA1F4N 35a	SOT-23	-	BCR 192, DTA 124XK, KSR 2107, RN 2408
FN 1 F4Z	Nec	Si-P+R	=AN 1F4Z: SMD	IFA1F4Z 35a	SOT-23	-	DTA 124TK, KSR 2111, UN 2117, 2SA1589
FN 1 L3M	Nec	Si-P+R	=AN 1L3M: SMD	IFA1L3M 35a	SOT-23	-	DTA 143EK, RN 2401, UN 211L, 2SA1655,++
FN 1 L3N	Nec	Si-P+R	=AN 1L3N: SMD	IFA1L3N 35a	SOT-23	-	DTA 143XK, KSR 2105, UN 211E, 2SA1653
FN 1 L3Z	Nec	Si-P+R	=AN 1L3Z: SMD	IFA1L3Z 35a	SOT-23	-	DTA 143TK, RN 2410, UN 2116, 2SA1510,++
FN 1 L4L	Nec	Si-P+R	=AN 1L4L: SMD	IFA1L4L 35a	SOT-23	-	DTA 144WK, RN 2409, UN 211E, 2SA1343,++
FN 1 L4M	Nec	Si-P+R	=AN 1L4M: SMD	IFA1L4M 35a	SOT-23	-	DTA 144EK, RN 2404, UN 2113, 2SA1341,++
FN 1 L4Z	Nec	Si-P+R	=AN 1L4Z: SMD	IFA1L4Z 35a	SOT-23	-	DTA 144TK, KSR 2112, UN 2110, 2SA1508
FND 500		Opto					
FO		Si-P	=2SA1202-O (SMD-Marking)	39	SOT-89		=2SA1202
FO		Si-N	=2SC2716-O (SMD-Marking)	35	SOT-23		=2SC2716
FO		Si-P	=KTA1662-O (SMD-Marking)	39	SOT-89		=KTA 1662
FO		Si-N	=KTC3878-O (SMD-Marking)	35	SOT-23		=KTC 3878
FOI		N-FET	=SO 4416 (SMD-Marking)	35	SOT-23		=SO 4416
FP		Z-Di	=SM 6T 68 (SMD-Marking)	71a(6x4mm)	SOD-6		=SM 6T....
FP 1 A3M...L3N	Nec	Si-P+R	=AP 1A3M...L3N: SMD	{FB1... 35a	SOT-23		-
FP 3 V50	Shi	MOS-N-FET-e	=2SK1245				
FP 3 V90	Shi	MOS-N-FET-e	=2SK1535				
FP 5 V50	Shi	MOS-N-FET-e	=2SK1247				
FP 08 C	Hit	Triac	200V, 30A-(Tc=90°C), Igt/Ih=50/30mA	21b	TO-48		T 6417..., T 6410..., 2N5444...5446
FP 08 D		Triac	=FP 08C: 300V	21b	TO-48		T 6417..., T 6410..., 2N5445...5446
FP 08 E		Triac	=FP 08C: 400V	21b	TO-48		T 6417..., T 6410..., 2N5445...5446
FP 08 F		Triac	=FP 08C: 500V	21b	TO-48		T 6417..., T 6410..., 2N5446
FP 08 G		Triac	=FP 08C: 600V	21b	TO-48		T 6417..., T 6410..., 2N5446
FP 10 V25	Shi	MOS-N-FET-e	=2SK1394				
FP 10 W50	Shi	MOS-N-FET-e	=2SK1523				
FP 15 W50	Shi	MOS-N-FET-e	=2SK1524				
FPQ 3467	Fch	Si-P	4x PNP Trans., 40V, 1A, >175MHz, <40/-ns	14-DIP	TO-116		-
FPQ 3468	Fch	Si-P	4x PNP Trans., 50V, 1A, >150MHz, <40/-ns	14-DIP	TO-116		-
FPQ 3724	Fch	Si-N	4x NPN Trans., 40V, 1A, >300MHz, <35/-ns	14-DIP	TO-116		CA 1724, DH 3724, MPQ 3724, SP 3724
FPQ 3725	Fch, Rca	Si-N	4x NPN Trans., 50V, 1A, >300MHz, <35/-ns	14-DIP	TO-116		CA 1725, DH 3725, FPQ 3725, SP 3725
FPT 6004		Si-P-Darl	=BD 902	17j	TO-220	BD 902	17j
FPT 6005		Si-N-Darl	=BD 901	17j	TO-220	BD 901	17j
FQ		Si-P	=2SA1037-FQ (SMD-Marking)	=35	(MMT)		=2SA1037
FQ		Si-P	=2SA1037K-Q (SMD-Marking)	35	SOT-23		=2SA1037K
FQ		Si-P	=2SA1576-Q (SMD-Marking)	35(2mm)	SOT-323		=2SA1576
FQ		Si-P	=2SA1774-FQ (SMD-Marking)	35(1,6mm)	SS Mini		=2SA1774
FQ		Si-P	=2SB1610 (SMD-Marking)	=35	(T Mini)		=2SB1610
FQ		Si-P	=2SB1618 (SMD-Marking)	35(2mm)	SOT-323		=2SB1618
FQ		Z-Di	=SM 6T 68A (SMD-Marking)	71a(6x4mm)	SOD-6		=SM 6T....
FQ 08 C	Hit	Triac	200V, 20A-(Tc=100°C), Igt/Ih=50/30mA	21b	TO-48		TXE 99..., SC 260..., T 6411..., T 6410...
FQ 08 D		Triac	=FQ 08C: 300V	21b	TO-48		TXE 99..., SC 260..., T 6411..., T 6410...
FQ 08 E		Triac	=FQ 08C: 400V	21b	TO-48		TXE 99..., SC 260..., T 6411..., T 6410...
FQ 08 F		Triac	=FQ 08C: 500V	21b	TO-48		TXE 99..., SC 260..., T 6411..., T 6410...
FQ 08 G		Triac	=FQ 08C: 600V	21b	TO-48		TXE 99..., SC 260..., T 6411..., T 6410...
FQ 3467	Fch	Si-P	=FPQ 3467: SMD	14-MDIP	TO-86		-
FQ 3468	Fch	Si-P	=FPQ 3468: SMD	14-MDIP	TO-86		-
FQ 3724	Fch	Si-N	=FPQ 3724: SMD	14-MDIP	TO-86		-
FQ 3725	Fch	Si-N	=FPQ 3725: SMD	14-MDIP	TO-86		-
FR		Si-P	=2SA1034-R (SMD-Marking)	35	SOT-23		=2SA1034
FR		Si-P	=2SA1037-FR (SMD-Marking)	=35	(MMT)		=2SA1037
FR		Si-P	=2SA1037K-R (SMD-Marking)	35	SOT-23		=2SA1037K
FR		Si-P	=2SA1531-R (SMD-Marking)	35(2mm)	SOT-323		=2SA1531
FR		Si-P	=2SA1576-R (SMD-Marking)	35(2mm)	SOT-323		=2SA1576
FR		Si-P	=2SA1774-FR (SMD-Marking)	35(1,6mm)	SS Mini		=2SA1774
FR		Si-N	=2SC2716-R (SMD-Marking)	35	SOT-23		=2SC2716
FR		Si-N	=2SC4988 (SMD-Marking)	39	SOT-89		=2SC4988
FR		Si-N	=2SD2472 (SMD-Marking)	=35	(T Mini)		=2SD2472
FR		Si-N	=2SD2482 (SMD-Marking)	35(2mm)	SOT-323		=2SD2482
FR		Si-N	=KTC3878-R (SMD-Marking)	35	SOT-23		=KTC 3878
FR 1/....		Si-Di	Rr			1N4007	31a
FR 2/-02....-12	Fjd	Si-Di	Rr, Uni, 200...1200V, 1,1A, Uf<1,1V(2A)	31a	(6x9mm0)	1N4007	31a
FR 34	Scs	Si-Di	Rr, Uni, 100V, 0,2A, Uf<1V(0,2A)	31a	DO-7	BA 159	31a
FR 3205 CC	Fch	Si-Di	Dual, 50V, 32A(Tc=130°), Uf<0,95V(16A), <50ns	16	TO-247		BYT 30P/200, BYV 72/50, BYW 99P/50
FR 3210 CC	Fch	Si-Di	=FR 3205: 100V	16	TO-247		BYT 30P/200, BYV 72/100, BYW 99P/100
FR 3215 CC	Fch	Si-Di	=FR 3205: 150V	16	TO-247		BYT 30P/200, BYV 72/150, BYW 99P/150
FR 3220 CC	Fch	Si-Di	=FR 3205: 180V	16	TO-247		BYT 30P/200, BYV 72/200, BYW 99P/200
FR 4001		Ge-Di	=AY 103K	3			=AY 103K
FR 4001 [Thomson]	Tho	Si-Di	=BYX 58/400			=BYX 58/...	
FRH 101		Si-Di	=1N4001			1N4007	31a
FRM 3205 CC	Fch	Si-Di	Dual, 50V, 32A(Tc=107°), Uf<0,95V(16A), <50ns	23	TO-3		BYT 30P/200, BYV 72/50, BYW 99P/50
FRM 3210 CC	Fch	Si-Di	=FRM 3205: 100V	23	TO-3		BYT 30P/200, BYV 72/100, BYW 99P/100
FRM 3215 CC	Fch	Si-Di	=FRM 3205: 150V	16	TO-3		BYT 30P/200, BYV 72/150, BYW 99P/150
FRM 3220 CC	Fch	Si-Di	=FRM 3205: 180V	16	TO-3		BYT 30P/200, BYV 72/200, BYW 99P/200
FRP 805	Fch	Si-Di	P FRr, 50V, 8A(Tc=130°), Uf<0,95V(8A), <50ns	17k	TO-220		BYP 21-50, BYT 79/300, BYW 29/50, FE 8A
FRP 810	Fch	Si-Di	=FRP 805: 100V	17k	TO-220		BYP 21-100, BYT 79/300, BYW 29/100, FE8B
FRP 815	Fch	Si-Di	=FRP 805: 150V	17k	TO-220		BYP 21-150, BYT 79/300, BYW 29/150, FE8C
FRP 820	Fch	Si-Di	=FRP 805: 180V	17k	TO-220		BYP 21-200, BYT 79/300, BYW 29/200, FE8D

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
FRP 840	Fch	Si-Di	P FRr, 400V, 8A(Tc=130°), Uf<1.5V(8A), <75ns	17k			BYT 79/400, BYV 29/400, FE 8G
FRP 850	Fch	Si-Di	=FRP 840: 500V	17k			BYT 79/500, BYV 29/500, FE 8H
FRP 860	Fch	Si-Di	=FRP 840: 600V	17k			BYT 12P/600, FE 8J
FRP 1005	Fch	Si-Di	P FRr, 50V, 10A(117°), Uf<1V(10A), <50ns	17k			BYT 79/300, BYV 79/50
FRP 1010	Fch	Si-Di	=FRP 1005: 100V	17k			BYT 79/300, BYV 79/100
FRP 1015	Fch	Si-Di	=FRP 1005: 150V	17k			BYT 79/300, BYV 79/150
FRP 1020	Fch	Si-Di	=FRP 1005: 180V	17k			BYT 79/300, BYV 79/200
FRP 1605	Fch	Si-Di	P FRr, 50V, 16A(Tc=118°), Uf<0.95V(16A), <50ns	17k			BYV 79/50, MUR 1505
FRP 1610	Fch	Si-Di	=FRP 1605: 100V	17k			BYV 79/100, MUR 1510
FRP 1615	Fch	Si-Di	=FRP 1605: 150V	17k			BYV 79/150, MUR 1515
FRP 1620	Fch	Si-Di	=FRP 1605: 180V	17k			BYV 79/200, MUR 1520
FRP 1605...1620 CC		Si-Di	=FRP 1605...1620: Dual	17e			BYV 32/..., BYP 22/..., FE 16A...D
FRP 2005 CC	Fch	Si-Di	Dual, 50V, 20A(Tc=117°), Uf<1V(10A), <50ns	17e			BYW 51/50, BYP 22-50, BYV 44/300
FRP 2010 CC	Fch	Si-Di	=FRP 2005CC: 100V	17e			BYW 51/100, BYP 22-100, BYV 44/300
FRP 2015 CC	Fch	Si-Di	=FRP 2005CC: 150V	17e			BYW 51/150, BYP 22-150, BYV 44/300
FRP 2020 CC	Fch	Si-Di	=FRP 2005CC: 180V	17e			BYP 22-200, BYV 44/300
FS		Si-P	=2SA1034-S (SMD-Marking)	35			*2SA1034
FS		Si-P	=2SA1037-FS (SMD-Marking)	-35			*2SA1037
FS		Si-P	=2SA1037K-S (SMD-Marking)	35			*2SA1037K
FS		Si-P	=2SA1531-S (SMD-Marking)	35(2mm)			*2SA1531
FS		Si-P	=2SA1576-S (SMD-Marking)	35(2mm)			*2SA1576
FS		Si-P	=2SA1763 (SMD-Marking)	35(2mm)			*2SA1763
FS		Si-P	=2SA1764 (SMD-Marking)	35			*2SA1764
FS		Si-P	=2SA1774-FS (SMD-Marking)	35(1,6mm)			*2SA1774
FS		Si-P	=2SB1611 (SMD-Marking)	-35			*2SB1611
FS		Si-P	=2SB1619 (SMD-Marking)	35(2mm)			*2SB1619
FS 1/...		Si-Di	=RGP 10G...M		BYD 33 M	31a	*RGP 10G...M
FSM 3 B2	Hit	Triac	200V, 3A-(Tc=67°C), Igt/Ih=40/20mA	13e			TAG 136... Z0 410...
FSM 3 B4		Triac	=FSM 3B2: 400V	13e			TAG 136... Z0 410...
FSM 6 B2	Hit	Triac	200V, 6A-(Tc=103°C), Igt/Ih=30/20mA	17b			T 2856... TAG 426... TAG 452...
FSM 6 B4		Triac	=FSM 6B2: 400V	17b			T 2856... TAG 426... TAG 452...
FSM 10 B4	Hit	Triac	400V, 10A-(Tc=100°C), Igt/Ih=30/20mA	17b			TAG 457... (BT 162... TAG 257...) ³
FSM 16 C2	Hit	Triac	200V, 16A-(Tc=76°C), Igt/Ih=50/30mA	65e			MAC 515... MAC 525... MAC 515A...
FSM 16 C4		Triac	=FSM 16C2: 400V	65e			MAC 515... MAC 525... MAC 515A...
FSM 16 C6		Triac	=FSM 16C2: 600V	65e			MAC 515... MAC 525... MAC 515A...
FSM 20 C2	Hit	Triac	=FSM 16C2: 20A(Tc=74°C)	65e			MAC 525... MAC 525A...
FSM 20 C4		Triac	=FSM 16C4: 20A(Tc=74°C)	65e			MAC 525... MAC 525A...
FSM 30 C2		Triac	=FSM 16C2: 30A(Tc=63°C)	65e			(MAC 50... MAC 50A... TAG 740...) ⁴
FSM 30 C4		Triac	=FSM 16C4: 30A(Tc=63°C)	65e			(MAC 50... MAC 50A... TAG 740...) ⁴
FSP 100 DC	Fch	CMOS-IC	Progr. Digital Filter	40-DIP			-
FSP 100 LC		CMOS-IC	=FSP 100DC:	44-LCC			-
FT							
FT		Si-P	=2SA1034-T (SMD-Marking)	35			*2SA1034
FT		Si-P	=2SA1531-T (SMD-Marking)	35(2mm)			*2SA1531
FT		Si-N	=2SC4146 (SMD-Marking)	35			*2SC4146
FT		Si-N	=2SD2473 (SMD-Marking)	-35			*2SD2473
FT		Si-N	=2SD2483 (SMD-Marking)	35(2mm)			*2SD2483
FT 1 M,N,P	Fjd	Si-Di	FRr, 140...600V, 0,3A, Uf<1,5V(1A), <3µs M=600V, N=300V, P=140V	31a	BA 159	31a	BA 157...159, BY 204/..., BY 208/..., ++
FT 06 B	Hit	Triac	100V, 6A-(Tc=88°C), Igt<75mA	22a			TAG 260... TAG 265... T 4700...
FT 06 C		Triac	=FT 06B: 200V	22a			TAG 260... TAG 265... T 4700...
FT 06 D		Triac	=FT 06B: 300V	22a			TAG 260... TAG 265... T 4700...
FT 06 E		Triac	=FT 06B: 400V	22a			TAG 260... TAG 265... T 4700...
FT 07 C	Hit	Triac	200V, 6A-(Tc=90°C), Igt/Ih=50/20mA	22a			TAG 260... TAG 265... T 4700...
FT 07 D		Triac	=FT 07C: 300V	22a			TAG 260... TAG 265... T 4700...
FT 07 E		Triac	=FT 07C: 400V	22a			TAG 260... TAG 265... T 4700...
FT 07 F		Triac	=FT 07C: 500V	22a			TAG 260... TAG 265... T 4700...
FT 07 G		Triac	=FT 07C: 600V	22a			TAG 260... TAG 265... T 4700...
FT 08 C	Hit	Triac	200V, 6A-(Tc=110°C), Igt/Ih=50/20mA	21b			BS6...A, TW6N...C, BS8...A, TW8N...C, ++
FT 08 D		Triac	=FT 08C: 300V	21b			BS6...A, TW6N...C, BS8...A, TW8N...C, ++
FT 08 E		Triac	=FT 08C: 400V	21b			BS6...A, TW6N...C, BS8...A, TW8N...C, ++
FT 08 F		Triac	=FT 08C: 500V	21b			BS6...A, TW6N...C, BS8...A, TW8N...C, ++
FT 08 G		Triac	=FT 08C: 600V	21b			BS6...A, TW6N...C, BS8...A, TW8N...C, ++
FT 12 C	Hit	Triac	200V, 6A-, Igt/Ih=75/20mA	17j			MAC 216... T 2801... SC 141... BS7...
FT 12 E		Triac	=FT 12C: 400V	17j			MAC 216... T 2801... SC 141... BS7...
FT 17	Fch	Si-N	UHF, -15V, >1GHz, PQ>35mW(1GHz)	2a			BF 357, BF 378...379, BFW 30, BFX 59, ++
FT 034 A	Fch	Si-N	S P, 150/80V, 10A, 15W(Tc=100°), >80MHz, <0,5/1µs	49m			2N5542
FT 034 B	Fch	Si-N	=FT 34A: 120/60V	49m			2N5542
FT 034 C	Fch	Si-N	S, 150/80V, 5A, 0,8W, >80MHz, <0,5/1µs	2a			BU 125, BUY 48...49, BUY 80...81, ++
FT 034 D	Fch	Si-N	=FT 34C: 120/60V	2a			BU 125, BUY 48...49, BUY 80...81, ++
FT 40	Sgs	Si-N	UHF, 15/10V, 0,3W, 1,4GHz, RadH	2a			-
FT 45	Sgs	Si-N	VHF, 30/30V 0,2W, >425MHz	5g			BF 173, BF 199, BF 224, BF 311, BF 373++
FT 107 A	Fch	Si-N	LF, In, 30/30V, 0,05A, 0,26W, hFE>1200, F<3dB	2a			2SC3112...13, 2SD1010...11, 2SD1512
FT 107 B	Fch	Si-N	=FT 107A: 45/45V, hFE=600...1550	2a			2SC3112...13, 2SD1010...11, 2SD1512
FT 107 C	Fch	Si-N	=FT 107A: 60/60V, hFE=150...950	2a			2N2483...2484, 2N3117, 2SD1011, 2SD1512++
FT 109	Fch	Si-N	HFS, 15/6V, 0,2A, 0,3W, >600MHz	2a			BSS 10...12, BSY 17...18, 2N2369(A), ++
FT 118	Fch	Si-N	VHF, 20/20V, 0,175W, 500MHz	5k			BF 173, BF 199, BF 224, BF 311, BF 373++
FT 123	Fch	Si-N	Vid, -/300V, 0,1A, 1W, >60MHz	2a			BF 259, BF 659, BFS 89, 2N5058
FT 317(A)		Si-N	=BD 237		BD 237	14h	=BD 237
FT 400A,B	Fch	Si-P	LF P, 80/80V, 8A, 30W(Tc=100°), 120MHz	49a			2N6186...6189
FT 401	Fch	Si-N	S P, -/400V, 2A, 100W, >2MHz	23a			BUX 46, 2SC3091, 2SC3099, 2SC3155, ++
FT 402	Fch	Si-N	=FT 401: 3,5A	23a			BUX 46, 2SC3091, 2SC3099, 2SC3155, ++
FT 410	Fch	Si-N	S P, -/200V, 7,5A, 100W, 5MHz	23a			BUX 47, 2SC3090, 2SC3092, 2SD811, ++
FT 411	Fch	Si-N	=FT 410: -/300V	23a			BUX 47, 2SC3090, 2SC3092, 2SD811, ++
FT 413	Fch	Si-N	S P, -/400V, 7,5A, 100W, 5MHz	23a			BUX 47, 2SC3090, 2SC3092, 2SD811, ++
FT 417(A)		Si-P	=BD 238		BD 238	14h	=BD 238
FT 423	Fch	Si-N	S P, -/400V, 7,5A, 100W, 5MHz	23a			BUX 47, 2SC3090, 2SC3092, 2SD811, ++
FT 430	Fch	Si-N	S P, -/400V, 10A, 100W, hFE=15...45	23a			BUS 12, BUW 26, BUW 12, BUW 35...36, ++
FT 431	Fch	Si-N	=FT 430: hFE=15...35	23a			BUS 12, BUW 26, BUW 12, BUW 35...36, ++
FT 0654(A...C)	Fch	N-FET	=FE 0654(A...C):	2b			=FE 0654(A...C)
FT 0655(A...C)	Fch	N-FET	=FE 0655(A...C):	2b			=FE 0655(A...C)
FT 701	Fch	MOS-P-FET-e	Dual, 30V, 0,2A, Up<0,6V, 30/-ns	TO-77			(D-GbG-DS)

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
FT 703	Fch	MOS-P-FET-e	S, 40V, 0.5A, Up<0.6V, 66/-ns	5(DGSubS)		T0-72	-	
FT 704	Fch	MOS-P-FET-e	S, 25V, 20mA, Up<0.6V, 150/-ns	5(DGSubS)		T0-72	-	
FT 709	Fch	Si-N	=2N709	2a		TO-18	=2N709	
FT 1210	Fch	Si-N	=2N917	5k		TO-72	=2N917	
FT 1310	Fch	Si-N	SS, 5V, 0.3W, <15/-ns	2a		TO-18	BSS 10...12, BSY 17...18, 2N2368...69, ++	
FT 1315	Fch	Si-N	SS, 30V, 0.2A, 0.36W, >500MHz, 12/18ns	2a		TO-18	BSS 10...12, BSY 17...18, 2N2368...69, ++	
FT 1324(B,C)	Fch	Si-N	VHF, 25/10V, 0.5A, 0.36W, B: >800MHz, C: >640MHz	2a		TO-18	BFX 55, 2SC2852	
FT 1341	Fch	Si-N	S, 25/10V, 0.1A, 0.36W, >480MHz, <65/-ns	2a		TO-18	BSW 41, BSY 62...63, 2N706A, 2N708, ++	
FT 1702	Fui	Si-P	HFS, 12/12V, 0.1A, 0.3W, 700MHz, <60/75ns	2a		TO-18	BSV 21, BSW 25, BSW 37, BSX 36, ++	
FT 1718(A...E)	Fch	Si-P	Dual, -/40V, 0.1A, >400MHz, F<6dB(1kHz)	T0-78		(CBE-EBC-)	BFX 11, 2N3726...3727, 2N4015...4016	
FT 1724	Fch	Si-N	=2N1724	49a		TO-61	=2N1724	
FT 1725	Fch	Si-N	=2N1725	49a		TO-61	=2N1725	
FT 1746	Fui	Si-P	Uni, 35/30V, 0.36W, 150MHz	2a		TO-18	BC 213, BC 258, BC 308, BC 558, 2SA1295+	
FT 1869...1874	Fch	50Hz-Thy	=2N1869...1874	2a		TO-5	=2N1869...1874	
FT 1881...1885	Fch	50Hz-Thy	=2N1881...1885	2a		TO-5	=2N1881...1885	
FT 2009...2013	Fch	50Hz-Thy	=2N2009...2013	2a		TO-5	=2N2009...2013	
FT 2368	Fch	Si-N	=2N2368	2a		TO-18		
FT 2369	Fch	Si-N	=2N2369	2a		TO-18		
FT 2383	Fch	Si-N	=2N2383	2a		TO-18		
FT 2384	Fch	Si-N	=2N2384	2a		TO-18		
FT 2955		Si-P	=BD 204	17j		TO-220	BD 244 C	
FT 2974	Fch	Si-N	=2N2974: ΔUbe<1.5mV	T0-71		(EBC-EBC-)	=2N2974	
FT 2975	Fch	Si-N	=2N2975: ΔUbe<1.5mV	T0-71		(EBC-EBC-)	=2N2975	
FT 2978	Fch	Si-N	=2N2978: ΔUbe<1.5mV	T0-71		(EBC-EBC-)	=2N2978	
FT 2979	Fch	Si-N	=2N2979: ΔUbe<1.5mV	T0-71		(EBC-EBC-)	=2N2979	
FT 3055		Si-N	=BD 203	17j		TO-220	BD 243 C	
FT 3567	Fch	Si-N	=2N3567: 0.5W	8a		TO-105	=2N3567	
FT 3568	Fch	Si-N	=2N3568: 0.5W	8a		TO-105	=2N3568	
FT 3569	Fch	Si-N	=2N3569: 0.5W	8a		TO-105	=2N3569	
FT 3641	Fch	Si-N	=2N3641: 0.45W	8a		TO-105	=2N3641	
FT 3642	Fch	Si-N	=2N3642: 0.45W	8a		TO-105	=2N3642	
FT 3643	Fch	Si-N	=2N3643: 0.45W	8a		TO-105	=2N3643	
FT 3644	Fch	Si-P	=2N3644: 0.45W	8a		TO-105	=2N3644	
FT 3645	Fch	Si-P	=2N3645: 0.45W	8a		TO-105	=2N3645	
FT 3722	Fch	Si-N	=2N3722: 0.5W	8a		TO-105	=2N3722	
FT 3723	Fch	Si-N	=2N3723	2a		TO-5	=2N3723	
FT 3820	Fch	P-FET	=2N3820: 0.2W	8b		TO-106	=2N3820	
FT 4017...4025	Fch	Si-P	=2N4017...4025: 0.5W	T0-71		(EBC-EBC-)	=2N4017...4025 ⁵⁾	
FT 4354...4356	Fch	Si-P	=2N4354...4356: 0.5W	8a		TO-105	=2N4354...4356	
FT 5040...5041	Fch	Si-P	=2N5040...5041: 0.5W	8a		TO-105	=2N5040...5041	
FT 5415	Fch	Si-P	=2N5415: 0.5W	8a		TO-105	MPS-U60 ⁶⁾ 13m	
FT 7207 A	Fch	Si-N	LFS P, 120/80V, 5A, 30W(Tc=100°), >70MHz	49a		TO-59	2N5284...5285	
FT 7207 B	Fch	Si-N	=FT 7207A: 100/60V	49a		TO-59	2N5002, 2N5004, 2N5284...5285	
FU...FZ								
FU 1 M,N,P	Fjd	Si-Di	FRr, 140...600V, 0.2A, Uf<2.5V(0.5A), <400ns M=600V, N=300V, P=140V	31a	(6x9mm0)	BA 159	31a	BA 157...159, BY 204/..., BY 208/..., ++
FU 12 B	Hit	Triac	100V, 3A=, Igt/Ih=30/20mA	17j		TO-220	TAG 232-600	
FU 12 C		Triac	=FU 12B: 200V	17j		TO-220	TAG 232-600	
FU 12 D		Triac	=FU 12B: 300V	17j		TO-220	TAG 232-600	
FU 12 E		Triac	=FU 12B: 400V	17j		TO-220	TAG 232-600	
FV		PIN-Di	=1SV248 (SMD-Marking)	35 (2mm)		SOT-323	=1SV248	
FV		PIN-Di	=1SV250 (SMD-Marking)	35		SOT-23	=1SV250	
FV 1043		C-Di	=BB 103				=BB 103	
FX		Si-P	=2SB1571-FX (SMD-Marking)	39		SOT-89	=2SB1571	
FX		Z-Di	=SM 6T 100 (SMD-Marking)	71a(6x4mm)		SOD-6	=SM 6T....	
FX 107(A...C)	Fch	Si-N	=FT 107(A...C):	=24		TO-120	=24	
FX 914	Fch	Si-N	=2N914: 0.25W	=24		TO-120	=2N914 ⁶⁾	
FX 918	Fch	Si-N	=2N918: 0.25W	=24		TO-120	=2N918 ⁶⁾	
FX 2368...2369(A)	Fch	Si-N	=2N2368...2369(A): 0.25W	=24		TO-120	=2N2368...2369(A) ⁶⁾	
FX 2483...2484	Fch	Si-N	=2N2483...2484: 0.25W	=24		TO-120	=2N2483...2484 ⁶⁾	
FX 2894(A)	Fch	Si-P	=2N2894(A): 0.25W	=24		TO-120	=2N2894(A) ⁶⁾	
FX 3299...3300	Fch	Si-N	=2N3299...3300: 0.25W	=24		TO-120	=2N3299...3300 ⁶⁾	
FX 3502...3503	Fch	Si-P	=2N3502...3503: 0.25W	=24		TO-120	=2N3502...3503 ⁶⁾	
FX 3724...3725	Fch	Si-N	=2N3724...3725: 0.25W	=24		TO-120	=2N3724...3725 ⁶⁾	
FX 3962...3965	Fch	Si-P	=2N3962...3965: 0.25W	=24		TO-120	=2N3962...3965 ⁶⁾	
FX 4046...4047	Fch	Si-N	=2N4046...4047: 0.25W	=24		TO-120	=2N4046...4047 ⁶⁾	
FX 4207	Fch	Si-P	=2N4207: 0.25W	=24		TO-120	=2N4207 ⁶⁾	
FX 4960	Fch	Si-N	=2N4960: 0.25W	=24		TO-120	=2N4960 ⁶⁾	
FY		Si-P	=2SA1202-Y (SMD-Marking)	39		SOT-89	=2SA1202	
FY		Si-P	=2SB1571-FY (SMD-Marking)	39		SOT-89	=2SB1571	
FY		Si-N	=2SC2761-Y (SMD-Marking)	35		SOT-23	=2SC2761	
FY		Si-N	=2SC3661 (SMD-Marking)	35		SOT-23	=2SC3661	
FY		Si-N	=BSV 65RA (SMD-Marking)	35		SOT-23	=BSV 65RA	
FY		Si-P	=KTA1662-Y (SMD-Marking)	39		SOT-89	=KTA 1662	
FY		Si-N	=KTC3878-Y (SMD-Marking)	35		SOT-23	=KTC 3878	
FY		Z-Di	=SM 6T 100A (SMD-Marking)	71a(6x4mm)		SOD-6	=SM 6T....	
FZ		Si-P	=2SB1571-FZ (SMD-Marking)	39		SOT-89	=2SB1571	
FZ		Si-N	=BSV 65RB (SMD-Marking)	35		SOT-23	=BSV 65RB	
FZH 211 S	Sie	LIN-IC	Pegelwandler/Level Shift, 0...+70°			16-DIP	-	
FZH 215 S	Sie	LIN-IC	=FZH 211S: -25...+85°			16-DIP	-	
FZL 135 S		LIN-IC	Leistungstreiber/Power Driver				E 435E	
FZL 4141 D	Sie	LIN-IC	4x Treiber/Driver, Ucc=4,5...35V, 0...+70°			18-DIP	-	
FZL 4145 D	Sie	LIN-IC	=FZL 4141D: -25...+85°			18-DIP	-	
FZL 4146 G	Sie	LIN-IC	4x Treiber/Driver, Ucc=4,5...40V, -25...+125°			20-MDIP	-	
G								
G 1(p)		Si-N	=BFS 20 (SMD-Marking)	35		SOT-23	=BFS 20	
G 1 A...M	Gie	Si-Di	Rr, Uni, 50...1000V, 1A, Uf<1,2V(1A), 2µs A=50, B=100, D=200, G=400, J=600, K=800, M=1000V	31a		SOD-57	BY 126...127, BY 133...135, 1N4001...07, ++	
G 1		Si-N	=D70Y1.5T1 (SMD-Marking)	39		SOT-89	=D70Y1.5T1	
G 2		Si-P	=BF 550 (SMD-Marking)	35		SOT-23	=BF 550	

Original	Fabric.	Constr.	Info	{Comp. Fig.	JAEGER	Fig.	International
G 2		Si-N	=BF 599 (SMD-Marking)	35	SOT-23		•BF 599
G 2 A....M	Gie	Si-Di	Rr, Uni, 50...1000V, 2A, Uf<1,2V(2A), 2µ A=50, B=100, D=200, G=400, J=600, K=800, M=1000V	31a	SOD-57	BY 255	31a BY 251...255, BY 259/..., GP 20A...M, ++
G 2 N 2955		Si-P	=BD 318	23a	TO-3	BD 318	23a •BD 318
G 2 N 3055		Si-N	=BD 317	23a	TO-3	BD 317	23a •BD 317
G 3		Si-P	=BF 536 (SMD-Marking)	35	SOT-23		•BF 536
G 3		Si-Di	=1SS196 (SMD-Marking)	35	SOT-23		•1SS196
G 3		Si-P	=2SA1257-3 (SMD-Marking)	35	SOT-23		•2SA1257
G 3		Si-N	=2SC2107-G3 (SMD-Marking)	35	SOT-23		•2SC2107
G 3 A....M	Gie	Si-Di	Rr, Uni, 50...1000V, 3A, Uf<1,1V(3A), 3µ A=50, B=100, D=200, G=400, J=600, K=800, M=1000V	31a	SOD-64	BY 255	31a BY 251...255, GP 30A...M, 1N5400...08, ++
G 4		Si-N	=BFS 20R (SMD-Marking)	35	SOT-23		•BFS 20R
G 4		Si-P	=2SA1257-4 (SMD-Marking)	35	SOT-23		•2SA1257
G 4		Si-N	=2SC2107-G4 (SMD-Marking)	35	SOT-23		•2SC2107
G 4 A....M	Gie	Si-Di	Rr, Uni, 50...1000V, 3A, Uf<1,1V(3A), 3µs A=50, B=100, D=200, G=400, J=600, K=800, M=1000V	31a	SOD-64	BY 255	31a BY 251...255, GP 30A...M, 1N5400...08, ++
G 5		Si-P	=2SA1257-5 (SMD-Marking)	35	SOT-23		•2SA1257
G 5		Si-N	=2SC2107-G5 (SMD-Marking)	35	SOT-23		•2SC2107
G 5		Si-P	=BF 550R (SMD-Marking)	35	SOT-23		•BF 550R
G 5/2		Ge-Di	=0A 70	31a		AA 138	31a •0A 70
G 5/61		Ge-Di	=AA 119	31a		AA 119	31a •AA 119
G 6		Si-N	=2SC2107-G6 (SMD-Marking)	35	SOT-23		•2SC2107
G 6		Si-P	=BF 569 (SMD-Marking)	35	SOT-23		•BF 569
G 7		Si-P	=BF 579 (SMD-Marking)	35	SOT-23		•BF 579
G 8		Si-P	=BF 660 (SMD-Marking)	35	SOT-23		•BF 660
G 9		Si-P	=BF 767 (SMD-Marking)	35	SOT-23		•BF 767
G 11		MOS-N-FET-e	=2SK1133 (SMD-Marking)	35	SOT-23		•2SK1133
G 13		MOS-N-FET-e	=2SK1580 (SMD-Marking)	35(2mm)	SOT-323		•2SK1580
G 14		MOS-N-FET-e	=2SK1581 (SMD-Marking)	35	SOT-23		•2SK1581
G 16		MOS-N-FET-e	=2SK1590 (SMD-Marking)	35	SOT-23		•2SK1590
G 17		MOS-N-FET-e	=2SK1589 (SMD-Marking)	35	SOT-23		•2SK1589
G 18		MOS-N-FET-e	=2SK1582 (SMD-Marking)	35	SOT-23		•2SK1582
G 18		MOS-N-FET-e	=2SK1591 (SMD-Marking)	35	SOT-23		•2SK1591
G 19		MOS-N-FET-e	=2SK1657 (SMD-Marking)	35	SOT-23		•2SK1657
G 20		MOS-N-FET-e	=2SK1658 (SMD-Marking)	35(2mm)	SOT-323		•2SK1658
G 21		MOS-N-FET-e	=2SK1958 (SMD-Marking)	35(2mm)	SOT-323		•2SK1958
G 22		MOS-N-FET-e	=2SK2090 (SMD-Marking)	35(2mm)	SOT-323		•2SK2090
G 23		MOS-N-FET-e	=2SK2158 (SMD-Marking)	35	SOT-23		•2SK2158
G 61		Si-P	=BF 569R (SMD-Marking)	35	SOT-23		•BF 569R
G 81		Si-P	=BF 660R (SMD-Marking)	35	SOT-23		•BF 660R
G 088		Si-St	=BZ 102/0V7	31a		(1N4148)	31a •BZ 102/0V7
G 150	Sie	LIN-IC	Telecom, Teilnehmerschaltung (SLIC)		28-DIP		
G 580	Itt	Ge-Di	Uni, 20V, 0,2A, Uf<0,5V(10mA)	31a	DO-7	(AA 138)	31a AA 139, 1N270
G 6004		Si-P-Darl	=BD 700	15j		BD 902	17j •BD 700
G 6005		Si-N-Darl	=BD 699	15j		BD 901	17j •BD 699
G 8870		LIN-IC	=KT 3170				KT 3170, MT 8870
GA							
GA		Si-N	=µPA600T (SMD-Marking)	46	SOT-163		•µPA600T
GA		Si-N	=2SD1463-GA (SMD-Marking)	39	SOT-89		•2SD1463
GA		Si-Di	=BAW 78A (SMD-Marking)	39	SOT-89		•BAW 78A
GA		Si-N	=BFR 35 (SMD-Marking)	35	SOT-23		•BFR 35
GA		Si-P	=S 416 T (SMD-Marking)	35	SOT-23		•S 416 T
GA 1		Si-P	=2SB1871-GA1 (SMD-Marking)	39	SOT-89		•2SA1871
GA 1 A3Q	Nec	Si-N+R	=AA 1A3Q: SMD	(GN1A3Q 35a(2mm))	SOT-323		DTC 113ZU
GA 1 A4M	Nec	Si-N+R	=AA 1A4M: SMD	(GN1A4M 35a(2mm))	SOT-323		DTC 114EU, 2SC4398
GA 1 A4P	Nec	Si-N+R	=AA 1A4P: SMD	(GN1A4P 35a(2mm))	SOT-323		DTC 114YU
GA 1 A4Z	Nec	Si-N+R	=AA 1A4Z: SMD	(GN1A4Z 35a(2mm))	SOT-323		DTC 114TU
GA 1 F4M	Nec	Si-N+R	=AA 1F4M: SMD	(GN1F4M 35a(2mm))	SOT-323		DTC 124EU, 2SC4397
GA 1 F4N	Nec	Si-N+R	=AA 1F4N: SMD	(GN1F4N 35a(2mm))	SOT-323		DTC 124XU
GA 1 F4Z	Nec	Si-N+R	=AA 1F4Z: SMD	(GN1F4Z 35a(2mm))	SOT-323		DTC 124TU
GA 1 L3M	Nec	Si-N+R	=AA 1L3M: SMD	(GN1L3M 35a(2mm))	SOT-323		DTC 143EU
GA 1 L3N	Nec	Si-N+R	=AA 1L3N: SMD	(GN1L3N 35a(2mm))	SOT-323		DTC 143XU
GA 1 L3Z	Nec	Si-N+R	=AA 1L3Z: SMD	(GN1L3Z 35a(2mm))	SOT-323		DTC 143TU
GA 1 L4L	Nec	Si-N+R	=AA 1L4L: SMD	(GN1L4L 35a(2mm))	SOT-323		DTC 144WU
GA 1 L4M	Nec	Si-N+R	=AA 1L4M: SMD	(GN1L4M 35a(2mm))	SOT-323		DTC 144EU, 2SC4396
GA 1 L4Z	Nec	Si-N+R	=AA 1L4Z: SMD	(GN1L4Z 35a(2mm))	SOT-323		DTC 144TU
GA 2		Si-P	=2SB1871-GA2 (SMD-Marking)	39	SOT-89		•2SA1871
GA 3		Si-P	=2SB1871-GA3 (SMD-Marking)	39	SOT-89		•2SA1871
GA 100	Hfo	Ge-Di	Uni, 26V, 0,02A	31a		AA 133	31a AA 132...134, 1N34, 1N54, 1N60
GA 101	Hfo	Ge-Di	Uni, 50V, 0,015A	31a		AA 133	31a AA 132...134, 1N34, 1N54, 1N60
GA 102	Hfo	Ge-Di	Uni, 60V, 0,012A	31a		AA 133	31a AA 132...134, 1N34, 1N54, 1N60
GA 103	Hfo	Ge-Di	Uni, 90V, 0,01A	31a		AA 133	31a AA 117...118, AA 132...133
GA 104	Hfo	Ge-Di	Uni, 115V, 0,01A	31a		AA 133	31a AA 117...118, AA 132...133
GA 105	Hfo	Ge-Di	Uni, 26V, 0,02A	31a		AA 133	31a AA 132...134, 1N34, 1N54, 1N60
GA 106	Hfo	Ge-Di	S, 35V, 0,03A(ss), 500ns	31a		AA 133	31a AA 132...134, 1N34, 1N54, 1N60
GA 107	Hfo	Ge-Di	S, 90V, 0,15A(ss), 500ns	31a		AA 133	31a AA 132...134, 1N34, 1N54, 1N60
GA 108	Hfo	Ge-Di	Uni, 90V, 0,02A	31a		AA 133	31a AA 117...118, AA 132...133
(2)GA 109	Hfo	Ge-Di	FM Dem, 50V, 0,015A	31a		AA 138	31a AA 113, 1N34, 1N54, 1N60
(2)GA 113	Hfo	Ge-Di	Dem, Diskr, 35V, 0,03A(ss)	31a		AA 138	31a AA 113, AA 119, 1N34, 1N54, 1N60
(4)GA 114	Hfo	Ge-Di	4x Ge-Di, Ring-Dem, 35V, 0,03A(ss)	31a			•4x GA 113
GA 5005(A....T)	Gie,Tho	Si-Di	TV-Booster-Di, 6...7kV, 0,3...0,44/3A, Uf<10V(0,5A)				
GAY 60	Hfo	Ge-Di	Uni, S, 20V, 0,075A	31a			AA 132...134, 1N34, 1N54, 1N60
GAY 61	Hfo	Ge-Di	Uni, S, 20V, 0,1A	31a			AA 135...136, AA 139
GAY 62	Hfo	Ge-Di	Uni, S, 20V, 0,1A	31a			AA 135...136, AA 139
GAY 63	Hfo	Ge-Di	Uni, S, 40V, 0,1A	31a			AA 136, 1N270
GAY 64	Hfo	Ge-Di	Uni, S, 80V, 0,075A	31a			1N270
GAZ 14	Hfo	Ge-Di	S, 25V, 0,02A, 500ns	31a			AA 132...134, 1N34, 1N54, 1N60
GAZ 15	Hfo	Ge-Di	Uni, S, 25V, 0,02A	31a			•GAZ 14
GAZ 16	Hfo	Ge-Di	=GAZ 14	31a			•GAZ 14
GAZ 17	Hfo	Ge-Di	=GAZ 15	31a			•GAZ 15

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
GB								
GB		Si-N	=2SD1463-GB (SMD-Marking)	39	SOT-89		+2SD1463	
GB		Si-Di	=BAW 78B (SMD-Marking)	39	SOT-89		+BAW 78B	
GB		Si-N	=BFR 35A (SMD-Marking)	35	SOT-23		+BFR 35A	
GB 1		Si-P	=2SB1578-GB1 (SMD-Marking)	39	SOT-89		+2SA1578	
GB 2		Si-P	=2SB1578-GB2 (SMD-Marking)	39	SOT-89		+2SA1578	
GB 3		Si-P	=2SB1578-GB3 (SMD-Marking)	39	SOT-89		+2SA1578	
GBC 107		Si-N	=BC 237	7a	TO-92	BC 546	7a	+BC 237
GBC 108		Si-N	=BC 238	7a	TO-92	BC 546	7a	+BC 238
GBC 109		Si-N	=BC 239	7a	TO-92	BC 550	7a	+BC 239
GBD 179		Si-N	=BD 179	14h	TO-126	BD 237	14h	+BD 179
GBD 189		Si-N	=BD 189	14h	TO-126	BD 189	14h	+BD 189
GBD 190		Si-P	=BD 190	14h	TO-126	BD 190	14h	+BD 190
GBD 266		Si-P-Darl	=BD 700	15j		BD 902	17j	+BD 700
GBD 267		Si-N-Darl	=BD 699	15j		BD 901	17j	+BD 699
GBD 645		Si-N-Darl	=BD 699	15j		BD 901	17j	+BD 699
GBD 646		Si-P-Darl	=BD 700	15j		BD 902	17j	+BD 700
GC								
GC		Si-N	=2SC2734 (SMD-Marking)	35	SOT-23		+2SC2734	
GC		Si-N	=2SC4264 (SMD-Marking)	35(2mm)	SOT-323		+2SC4264	
GC		Si-Di	=BAW 78C (SMD-Marking)	39	SOT-89		+BAW 78C	
GC 100	Hfo	Ge-P	LF Imp 15V, 15mA, 0,03W	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 101	Hfo	Ge-P	LF Imp, 15V, 15mA, 0,03W	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 102	Hfo	Ge-P	LF Imp,Drv, 15V, 50mA	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 103	Hfo	Ge-P	LF Imp, 15V, 15mA	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 104	Hfo	Ge-P	=GC 103: In	2a		AC 151	2a	AC 151r, ACY 32
GC 111	Hfo	Ge-P	LF, 80V, 0,125A, 0,07W	2a				ACY 39, 2N2042...2043
GC 112	Hfo	Ge-P	LF, 80V, 0,125A, 0,07W	2a				ACY 39, 2N2042...2043
GC 115	Hfo	Ge-P	LF Imp,Drv, 20V, 0,15A, 0,07W	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 116	Hfo	Ge-P	LF Imp,Drv, 20V, 0,15A, 0,07W	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 117	Hfo	Ge-P	=GC 116: In	2a		AC 151	2a	AC 151r, ACY 32
GC 118	Hfo	Ge-P	=GC 116: In	2a		AC 151	2a	AC 151r, ACY 32
GC 120	Hfo	Ge-P	LF Drv,Out, 20V, 0,15A, 0,07W	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188
GC 121	Hfo	Ge-P	LF Drv,Out, 20V, 0,15A, 0,07W	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188
GC 122	Hfo	Ge-P	LF, S, 30V, 0,15A, 0,07W	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188
GC 123	Hfo	Ge-P	=GC 122: 60V	2a				ACY 24, ASY 48, ASY 77
GC 181(A)[Grundig]		Si-P	=BC 181	7e		BC 556	7a	+BC 181
GC 189 [Grundig]		Si-N	=BC 238	7e		BC 546	7a	+BC 238
GC 195 [Grundig]		Si-N-Darl	=BC 517	7a, 7e		(BC 879)	7c	+BC 517
GC 196 [Grundig]		Si-N	=BC 337	7e		BC 337	7a	+BC 337
GC 197 [Grundig]		Si-P	=BC 327	7e		BC 327	7a	+BC 327
GC 198 [Grundig]		Si-P	=BC 161			BC 161	2a	+BC 161
GC 214 [Grundig]		Si-P	=BC 214	7a		BC 560	7a	+BC 214
GC 216	Hfo	Ge-P	LF Drv,Out, 20V, 0,1A, 0,075W	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 217	Hfo	Ge-P	LF Drv,Out, 20V, 0,1A, 0,075W	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 221	Hfo	Ge-P	LF Drv,Out, 20V, 0,1A, 0,075W	2a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 223	Hfo	Ge-P	=GC 221: 60V	2a				ACY 24, ASY 48, ASY 77
GC 223(A,B)[Grun.]		Si-N	=BC 337	7a		BC 337	7a	+BC 337
GC 237 [Grundig]		Si-N	=BC 237	7a		BC 546	7a	+BC 237
GC 238 [Grundig]		Si-N	=BC 238	7a		BC 546	7a	+BC 238
GC 239 [Grundig]		Si-N	=BC 239	7a		BC 550	7a	+BC 239
GC 269 [Grundig]		Si-P	=BC 328	7a		BC 327	7a	+BC 328
GC 300	Hfo	Ge-P	LF Out, 20V, 0,5A, 0,6W	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188
GC 301	Hfo	Ge-P	LF Drv,Out, 32V, 0,5A	2a		AC 188 K	3a	AC 128, AC 153, AC 188
GC 307 [Grundig]		Si-P	=BC 307	7a		BC 556	7a	+BC 307
GC 308 [Grundig]		Si-P	=BC 308	7a		BC 556	7a	+BC 308
GC 309 [Grundig]		Si-P	=BC 309	7a		BC 560	7a	+BC 309
GC 371 [Grundig]		Si-N	=BC 338	7a		BC 337	7a	+BC 338
GC 372 [Grundig]		Si-P	=BC 328	7a		BC 327	7a	+BC 328
GC 373 [Fairch.]		Si-N	=BC 368	7a		BC 337	7a	+BC 368
GC 373 [Valvo]		Si-N	=BC 368	7c		BC 639	7c	+BC 368
GC 374 [Fairch.]		Si-P	=BC 369	7a		BC 327	7a	+BC 369
GC 374 [Valvo]		Si-P	=BC 369	7c		BC 640	7c	+BC 369
GC 500	Hfo	Ge-P	LF Drv,Out, 24V, 0,3A, 0,55W	1a		AC 188 K	3a	AC 128, AC 152...153, AC 188
GC 501	Hfo	Ge-P	LF Drv,Out, 24V, 0,3A, 0,55W	1a		AC 188 K	3a	AC 128, AC 152...153, AC 188
GC 502	Hfo	Ge-P	LF Drv,Out, 32V, 0,3A, 0,55W	1a		AC 188 K	3a	AC 128, AC 152...153, AC 188
GC 503	Hfo	Ge-P	Min, LF, 7V, 5mA, 0,01W	37d				OC 57...60
GC 504	Hfo	Ge-P	Min, LF, 7V, 5mA, 0,01W	37d				OC 57...60
GC 505	Hfo	Ge-P	Min, LF, 7V, 5mA, 0,01W	37d				OC 57...60
GC 506	Hfo	Ge-P	Min, LF, 7V, 5mA, 0,01W	37d				OC 57...60
GC 507	Hfo	Ge-P	LF Drv 32V, 0,125A, 0,125W	1a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 508	Hfo	Ge-P	LF Drv 32V, 0,125A, 0,125W	1a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 509	Hfo	Ge-P	LF Drv 60V, 0,125A, 0,125W	1a				ACY 24, ASY 48, ASY 77
GC 510	Hfo	Ge-P	LF Out, 32V, 1A, 0,2W	1a		AC 188 K	3a	AC 128, AC 153, AC 188
GC 510 K	Hfo	Ge-P	=GC 510: 0,3W	3a		AC 188 K	3a	AC 128K, AC 153K, AC 188K
GC 511	Hfo	Ge-P	LF Out, 25V, 1A, 0,2W	1a		AC 188 K	3a	AC 128, AC 153, AC 188
GC 511 K	Hfo	Ge-P	=GC 511: 0,3W	3a		AC 188 K	3a	AC 128K, AC 153K, AC 188K
GC 512	Hfo	Ge-P	LF Out, 25V, 1A, 0,2W	1a		AC 188 K	3a	AC 128, AC 153, AC 188
GC 512 K	Hfo	Ge-P	=GC 512: 0,3W	3a		AC 188 K	3a	AC 128K, AC 153K, AC 188K
GC 515	Hfo	Ge-P	LF Drv,Out, 32V, 0,125A, 0,125W	1a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 516	Hfo	Ge-P	LF Drv,Out, 32V, 0,125A, 0,125W	1a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 517	Hfo	Ge-P	LF Drv,Out, 32V, 0,125A, 0,125W	1a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 518	Hfo	Ge-P	LF Drv,Out, 32V, 0,125A, 0,125W	1a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 519	Hfo	Ge-P	LF Drv,Out, 32V, 0,125A, 0,125W	1a		AC 151	2a	AC 122, AC 125...126, AC 151
GC 520	Hfo	Ge-N	LF Out, 32V, 1A, 0,2W	1a		AC 187 K	3a	AC 176, AC 187
GC 520 K	Hfo	Ge-N	=GC 520: 0,3W	3a		AC 187 K	3a	AC 176K, AC 187K
GC 521	Hfo	Ge-N	LF Out, 25V, 1A, 0,2W	1a		AC 187 K	3a	AC 176, AC 187
GC 521 K	Hfo	Ge-N	=GC 521: 0,3W	3a		AC 187 K	3a	AC 176K, AC 187K
GC 522	Hfo	Ge-N	LF Out, 20V, 1A, 0,2W	1a		AC 187 K	3a	AC 176, AC 187
GC 522 K	Hfo	Ge-N	=GC 522: 0,3W	3a		AC 187 K	3a	AC 176K, AC 187K
GC 525	Hfo	Ge-N	LF Drv,Out, 15V, 0,125A, 0,125W	1a		AC 187 K	3a	AC 127, AC 176, AC 187

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
GC 526	Hfo	Ge-N	LF Drv.Out, 32V, 0,125A, 0,125W	1a	AC 187 K	3a	AC 127, AC 176, AC 187
GC 527	Hfo	Ge-N	LF Drv.Out, 32V, 0,125A, 0,125W	1a	AC 187 K	3a	AC 127, AC 176, AC 187
GCN 53	Hfo	Ge-N	LF Drv.Out, 30V, 0,25A, 0,125W	1a	AC 187 K	3a	AC 127, AC 176, AC 187
GCN 54	Hfo	Ge-N	LF Drv.Out, 48V, 0,25A, 0,125W	1a			-
GCN 55	Hfo	Ge-P	LF Drv.Out, 32V, 0,125A, 0,125W	1a	AC 188 K	3a	AC 128, AC 152...153, AC 188
GCN 56	Hfo	Ge-P	LF Drv.Out, 60V, 0,125A, 0,125W	1a			ACY 24, ASY 48, ASY 77
GD							
GD		Si-Di	=BAW 78D (SMD-Marking)	39	SOT-89		=BAW 78D
GD 100	Hfo	Ge-P	LF P, 20V, 1,3A, 2W(Tc=45°)	22a	TO-66	AD 162	AD 162
GD 110	Hfo	Ge-P	LF P, 20V, 1,3A, 2W(Tc=45°)	22a	TO-66	AD 162	AD 162
GD 114 [Grundig]		Si-P	=BD 246B	16h		(BD 246 C) ⁵	=BD 246B
GD 115 [Grundig]		Si-N	=BD 245B	16h		(BD 245 C) ⁵	=BD 245B
GD 120	Hfo	Ge-P	LF P, 33V, 1,3A, 2W(Tc=45°)	22a	TO-66	AD 162	AD 162
GD 125	Hfo	Ge-P	LF P, 66V, 1,3A, 2W(Tc=45°)	22a	TO-66		-
GD 130	Hfo	Ge-P	LF P, 66V, 1,3A, 2W(Tc=45°)	22a	TO-66		-
GD 133 [Grundig]		Si-P	=BD 140	14h	TO-126	BD 238	=BD 140
GD 134 [Grundig]		Si-P	=BD 246B			BD 246 C	=BD 246B
GD 135 [Grundig]		Si-N	=BD 245B			BD 245 C	=BD 245B
GD 142 [Grundig]		Si-N	=2N3055	23a	TO-3	2N3055	=2N3055
GD 150	Hfo	Ge-P	LF P, 20V, 3A, 5,3W	22a	TO-66	(AD 162) ⁷	(AD 162, 2SB474) ⁷
GD 151 [Grundig]		Si-N	=BD 433	14h	TO-126	BD 189	=BD 433
GD 152 [Grundig]		Si-P	=BD 434	14h	TO-126	BD 190	=BD 434
GD 160(A...C)	Hfo	Ge-P	LF P, 20V, 3A, 5,3W	22a	TO-66	(AD 162) ⁷	(AD 162, 2SB474) ⁷
GD 170(A...C)	Hfo	Ge-P	=GD 160: 33V	22a	TO-66	(AD 162) ⁷	(AD 162, 2SB474) ⁷
GD 175(A...C)	Hfo	Ge-P	=GD 160: 50V	22a	TO-66		-
GD 180(A...C)	Hfo	Ge-P	=GD 160: 66V	22a	TO-66		-
GD 183 [Grundig]		Si-P	=BD 136	14h	TO-126	BD 140	=BD 136
GD 190	Hfo	Ge-P	LF P, 30V, 1,5A	22a	TO-66	AD 162	AD 162
GD 191	Hfo	Ge-P	LF P, 40V, 1,5A	22a	TO-66	AD 162	AD 162
GD 192	Hfo	Ge-P	LF P, 50V, 1,5A	22a	TO-66		-
GD 200	Hfo	Ge-P	LF P, 30V, 6A, 12W(Tc=50°)	23a	TO-3	AL 102	AL 102...103, AUY 22(A), AUY 28
GD 203 [Grundig]		Si-N	=BD 243B	17j	TO-220	BD 243 C	=BD 243B
GD 204 [Grundig]		Si-P	=BD 244B	17j	TO-220	BD 244 C	=BD 244B
GD 207 [Grundig]		Si-N	=BD 243B	17j	TO-220	BD 243 C	=BD 243B
GD 210	Hfo	Ge-P	LF P, 60V, 6A, 12W(Tc=50°)	23a	TO-3	AL 102	AL 102...103, AUY 22(A), AUY 28
GD 220	Hfo	Ge-P	LF P, 80V, 6A, 12W(Tc=50°)	23a	TO-3	AL 102	AL 102...103, AUY 22(A), AUY 28
GD 240	Hfo	Ge-P	LF S P, 30V, 3A, 10W	22a	TO-66	(AD 162) ⁷	(AD 162, 2SB474) ⁷
GD 241	Hfo	Ge-P	LF S P, 40V, 3A, 10W	22a	TO-66	(AD 162) ⁷	(AD 162, 2SB474) ⁷
GD 241(A,B)[Grun.]		Si-N	=BD 241A,B	17j	TO-220	BD 243 C	=BD 241A,B
GD 242	Hfo	Ge-P	LF S P, 50V, 3A, 10W	22a	TO-66		-
GD 243	Hfo	Ge-P	LF S P, 65V, 3A, 10W	22a	TO-66		-
GD 243 [Grundig]		Si-N	=BD 243	17j	TO-220	BD 243 C	=BD 243
GD 244	Hfo	Ge-P	LF S P, 75V, 3A, 10W	22a	TO-66		-
GD 340 [Grundig]		Si-P	=BD 438	14h	TO-126	BD 190	=BD 438
GD 341 [Grundig]		Si-N	=BD 437	14h	TO-126	BD 189	=BD 437
GD 361 [Grundig]		Si-N	=BD 433	14h	TO-126	BD 189	=BD 433
GD 362 [Grundig]		Si-P	=BD 434	14h	TO-126	BD 190	=BD 434
GD 363 [Grundig]		Si-N	=BD 433	14h	TO-126	BD 189	=BD 433
GD 364 [Grundig]		Si-P	=BD 434	14h	TO-126	BD 190	=BD 434
GD 384 [Grundig]		Si-N	=BD 525	13j		(2SC4135) ⁴	=BD 525
GD 607	Hfo	Ge-N	LF P, 32V, 1A, 4W(Tc=60°)	22a	TO-66	AD 161	AD 161
GD 608	Hfo	Ge-N	LF P, 25V, 1A, 4W(Tc=60°)	22a	TO-66	AD 161	AD 161
GD 609	Hfo	Ge-N	LF P, 20V, 1A, 4W(Tc=60°)	22a	TO-66	AD 161	AD 161
GD 617	Hfo	Ge-P	LF P, 32V, 1A, 4W(Tc=60°)	22a	TO-66	AD 162	AD 162
GD 618	Hfo	Ge-P	LF P, 25V, 1A, 4W(Tc=60°)	22a	TO-66	AD 162	AD 162
GD 619	Hfo	Ge-P	LF P, 20V, 1A, 4W(Tc=60°)	22a	TO-66	AD 162	AD 162
GE							
GE		Si-P	=2SA1455K-E (SMD-Marking)	35	SOT-23		=2SA1455K
GE		Si-Di	=BAW 79A (SMD-Marking)	39	SOT-89		=BAW 79A
GE		Si-N	=BFR 35AP (SMD-Marking)	35	SOT-23		=BFR 35AP
GE 1001	Gen,Rca	Si-Di	FRr, 50V, 1A, Uf<0,95V(1A), <35ns	31a	SOD-57	BYV 27/200	BYV 26B, EGP 10A, FE 1A
GE 1002	Gen,Rca	Si-Di	=GE 1001: 100V	31a	SOD-57	BYV 27/200	BYV 26B, EGP 10B, FE 1B
GE 1003	Gen,Rca	Si-Di	=GE 1001: 150V	31a	SOD-57	BYV 27/200	BYV 26B, EGP 10C, FE 1C
GE 1004	Gen,Rca	Si-Di	=GE 1001: 200V	31a	SOD-57	BYV 27/200	BYV 26B, EGP 10D, FE 1D
GE 1101	Gen,Rca	Si-Di	FRr, 50V, 2,5A, 0,95V(2A), <35ns	31a	SOD-57	BYV 28/200	BYV 28/50,EGP 30A, FE 3A
GE 1102	Gen,Rca	Si-Di	=GE 1101: 100V	31a	SOD-57	BYV 28/200	BYV 28/100,EGP 30B, FE 3B
GE 1103	Gen,Rca	Si-Di	=GE 1101: 150V	31a	SOD-57	BYV 28/200	BYV 28/150,EGP 30C, FE 3C
GE 1104	Ge,Rca	Si-Di	=GE 1101: 200V	31a	SOD-57	BYV 28/200	BYV 28/200,EGP 30D, FE 3D
GE 1301	Gen,Rca	Si-Di	FRr, 50V, 6A, 0,975V(2A), <35ns	31a	SOD-64		BYV 61, FE 6A
GE 1302	Gen,Rca	Si-Di	=GE 1301: 100V	31a	SOD-64		BYV 62, FE 6B
GE 1303	Gen,Rca	Si-Di	=GE 1301: 150V	31a	SOD-64		BYV 63, FE 6C
GE 1304	Gen,Rca	Si-Di	=GE 1301: 200V	31a	SOD-64		FE 6D
GE 3055 P	Gen	Si-N	LF S P, 80/80V, 10A, 70W	18j	TO-3P	BD 245 C	BD 245B...F, BD 545B...D, 2SD1187, ++
GE 5060	Gen	Si-N-Darl+Di	S P, 400/350V, 20/25A, 125W, hFE=160>100	23a	TO-3		BUT 13, MJ 10000...01, MJ 10004...05
GE 5061	Gen	Si-N-Darl+Di	=GE 5060: 450/400V	23a	TO-3		BUT 13, MJ 10000...01, MJ 10004...05
GE 5062	Gen	Si-N-Darl+Di	=GE 5060: 500/450V	23a	TO-3		BUT 13, MJ 10001, MJ 10005, MJ 10008...09
GE 6060	Gen	Si-N-Darl+Di	=GE 5060: integr. Speedup-Diode(E +B), hFE=160>40	23a	TO-3		MJ 10004...5, MJ 10008...09
GE 6061	Gen	Si-N-Darl+Di	=GE 5061: integr. Speedup-Diode(E +B), hFE=160>40	23a	TO-3		MJ 10004...5, MJ 10008...09
GE 6062	Gen	Si-N-Darl+Di	=GE 5062: integr. Speedup-Diode(E +B), hFE=160>40	23a	TO-3		MJ 10005, MJ 10008...09
GE 6251	Gen	Si-N-Darl+Di	S P, Speedup-Di., 450/400V, 10/15A, 125W, hFE>60	23a	TO-3		MJ 10006...07, MJ 10013...14
GE 6252	Gen	Si-N-Darl+Di	=GE 6251: 500/450V	23a	TO-3		MJ 10007, MJ 10013...14
GE 6253	Gen	Si-N-Darl+Di	=GE 6251: 550/500V	23a	TO-3		MJ 10013...14
GE 10000...10009	Gen	Si-N-Darl+Di	=MJ 10000...10009	23a	TO-3		=MJ 10000...10009
GE 10015...10016	Gen	Si-N-Darl+Di	=MJ 10015...10016	23a	TO-3		=MJ 10015...10016
GE 10020...10023	Gen	Si-N-Darl+Di	=MJ 10020...10023	23a	TO-3		=MJ 10020...10023
GE 13070P...13071P	Gen	Si-N	=MJ 13070...13071: 100W	18j	TO-3P	BUW 11 A	BUW 11(A), BU 131(A), BUV 82...83, ++
GE 13080P...13081P	Gen	Si-N	=MJ 13080...13081: 110W	18j	TO-3P	BUW 13 A	BUW 12(A), BU 132(A), BUP 22B...C, ++
GE 13080T...13081T	Gen	Si-N	=MJ 13080...13081: 90W	17j	TO-220	BUT 12 A	BUT 12(A), BUT 54(A), BUT 56(A), ++
GE 13100P...13101P	Gen	Si-N	=MJ 13100...13101: 125W	18j	TO-3P		BUX 98(A)P, 2SC3988
GER 4001...4007	Gen	Si-Di	=1N4001...4007	31a	SOD-57	1N4007	=1N4001...4007
GES 92	Gen	Si-N	Uni, 40/40V, 0,4A, 0,625W, 100MHz	7e	TO-92	BC 337	BC 337, BC 635, 2SC3377, 2SC3939, ++

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
GES 93	Gen	Si-P	Uni, 40/40V, 0.4A, 0.625W, 100MHz	7e	TO-92	BC 327	7a	BC 327, BC 636, 2SB910, 2SD1116, ++
GES 97	Gen	Si-N	Uni, 60/40V, 0.1A, 0.36W, 100MHz	7e	TO-92	BC 546	7a	BC 174, BC 546, 2SC2240, 2SC2459, ++
GES 98	Gen	Si-N	Uni, 80/60V, 0.1A, 0.36W, 100MHz	7e	TO-92	BC 546	7a	BC 546, 2SC2240, 2SC2459, 2SC3378, ++
GES 929...930	Gen	Si-N	=2N929...930: 0.36W	7e	TO-92	+2N929...930		+2N929...930
GES 2218...2219(A)	Gen	Si-N	=2N2218...2219(A): 0.625W	7e	TO-92	+2N2218...19		+2N2218...2219(A)
GES 2221...2222(A)	Gen	Si-N	=2N2221...2222(A): 0.36W	7e	TO-92	+2N2221...22		+2N2221...2222(A)
GES 2483	Gen	Si-N	=2N2483: 0.36W	7e	TO-92	+2N2483		+2N2483
GES 2646	Gen	UJT-P	=2N2646	7b	TO-29			+2N2646
GES 2647	Gen	UJT-P	=2N2647	7b	TO-92			+2N2647
GES 2904...2905(A)	Gen	Si-P	=2N2904...2905(A): 0.6W	7e	TO-92	+2N2904...05		+2N2904...2905(A)
GES 2906...2907(A)	Gen	Si-P	=2N2906...2907(A): 0.36W	7e	TO-92	+2N2906...07		+2N2906...2907(A)
GES 3053	Gen	Si-N	=2N3053: 0.625W	7e	TO-92	+BC 639	7c	BC 337A, BC 637, BC 639, 2SD1616, ++
GES 3414...3417	Gen	Si-N	=2N3414...3417: 0.625W	7e	TO-92	+2N3414...17		+2N3414...3417
GES 3565...3569	Gen	Si-N	=2N3565...3569: 0.625W	7e	TO-92	+2N3565...69		+2N3565...3569
GES 4121...4122	Gen	Si-P	=2N4121...4122: 0.2W	7e	TO-92	+2N4121...22		+2N4121...4122
GES 4248	Gen	Si-P	=2N4248: 0.4W	7e	TO-92			+2N4248
GES 4891...4894	Gen	UJT-P	=2N4891...4894	7b	TO-92			+2N4891...4894
GES 5305...5308(A)	Gen	Si-N	=2N5305...5308(A): 0.9W	7e	TO-92			+2N5305...5308(A)
GES 5368...5375	Gen	Si-N/P	=2N5368...5375: 0.36W	7e	TO-92			+2N5368...5375
GES 5401	Gen	Si-P	=2N5401	7e	TO-92			+2N5401
GES 5447...5451	Gen	Si-N/P	=2N5447...5451: 0.36W	7e	TO-92	+2N5447...51		+2N5447...5451
GES 5551	Gen	Si-N	=2N5551	7e	TO-92	+2N5551		+2N5551
GES 5810...5823	Gen	Si-N/P	=2N5810...5823: 0.5W	7c	TO-92			+2N5810...5823
GES 5824...5828(A)	Gen	Si-N	=2N5824...5828(A): 0.36W	7c	TO-92			+2N5824...5828(A)
GES 6000...6007	Gen	Si-N/P	=2N6000...6007: 0.4W	7e	TO-92			+2N6000...6007
GES 6010...6017	Gen	Si-N/P	=2N6010...6017: 0.5W	7e	TO-92			+2N6010...6017
GES 6027	Gen	PUT	=2N6027	7n	TO-92			+2N6027
GES 6028	Gen	PUT	=2N6028	7n	TO-92			+2N6028
GES 6218...6221	Gen	Si-N	=2N6218...6221: 0.5W	7e	TO-92			+2N6218...6221
GES 6222	Gen	Si-N	=2N6222: 0.36W	7e	TO-92			+2N6222
GES 6224	Gen	Si-N	=2N6224: 0.36W	7e	TO-92			+2N6224
GES 6426...6427	Gen	Si-N	=2N6426...6427: 0.625W	7e	TO-92			+2N6426...6427
GES 6560...6563	Gen	Si-N/P	=2N6560...6563: 0.625W	7e	TO-92			+2N6560...6563
GET 706	Gen	Si-N	=2N706: 0.36W	7a	SOT-30			+2N706
GET 708	Gen	Si-N	=2N708: 0.36W	7a	SOT-30			+2N708
GET 914	Gen	Si-N	=2N914: 0.36W	7a	SOT-30			+2N914
GET 929	Gen	Si-N	=2N929: 0.36W	7a	SOT-30			+2N929
GET 930	Gen	Si-N	=2N930: 0.36W	7a	SOT-30			+2N930
GET 2221(A)	Gen	Si-N	=2N2221(A): 0.36W	7a	SOT-30			+2N2221(A)
GET 2222(A)	Gen	Si-N	=2N2222(A): 0.36W	7a	SOT-30			+2N2222(A)
GET 2369	Gen	Si-N	=2N2369: 0.36W	7a	SOT-30			+2N2369
GET 2483	Gen	Si-N	=2N2483: 0.36W	7a	SOT-30			+2N2483
GET 2484	Gen	Si-N	=2N2484: 0.36W	7a	SOT-30			+2N2484
GET 2904...2907	Gen	Si-P	=2N2904...2907: 0.36W	7a	SOT-30			+2N2904...2907
GET 3013...3014	Gen	Si-N	=2N3013...3014: 0.36W	7a	SOT-30			+2N3013...3014
GET 3562...3563	Gen	Si-N	=2N3562...3563: 0.25W	7a	SOT-30			+2N3562...3563
GET 3638(A)	Gen	Si-P	=2N3638(A): 0.25W	7a	SOT-30			+2N3638(A)
GET 3646	Gen	Si-N	=2N3646: 0.36W	7a	SOT-30			+2N3646
GET 3903...3906	Gen	Si-N/P	=2N3903...3906: 0.31W	7a	SOT-30			+2N3903...3906
GET 4870	Gen	UJT-P	=2N4870:	7b	SOT-30			+2N4870
GET 4871	Gen	UJT-P	=2N4871:	7b	SOT-30			+2N4871
GET 5305...5308(A)	Gen	Si-N	=2N5305...5308(A): 0.4W	7a	SOT-30			+2N5305...5308(A)
GF								
GF		Si-Di	=BAW 79B (SMD-Marking)	39	SOT-89			+BAW 79B
GF		Si-N	=BFN 22 (SMD-Marking)	35	SOT-23			+BFN 22
GF		Si-N	=BFR 92P (SMD-Marking)	35	SOT-23			+BFR 92P
GF 100	Hfo	Ge-P	AM IF	2a	AF 239 S	5g		AF 127, AF 200, AF 139, AF 239(S)
GF 105	Hfo	Ge-P	AM Inp,Mx,Os	2a	AF 239 S	5g		AF 126, AF 200, AF 139, AF 239(S)
GF 108	Hfo	Ge-P	AM Inp,Mx,Os	2a	AF 239 S	5g		AF 126, AF 200, AF 139, AF 239(S)
GF 120	Hfo	Ge-P	AM Inp,Mx,IF, 30MHz	5k	AF 239 S	5g		AF 126, AF 200, AF 139, AF 239(S)
GF 121	Hfo	Ge-P	AM Inp,Mx, 50MHz	5k	AF 239 S	5g		AF 126, AF 200, AF 139, AF 239(S)
GF 122	Hfo	Ge-P	AM Inp,Mx,Os, 50MHz	5k	AF 239 S	5g		AF 126, AF 200, AF 139, AF 239(S)
GF 125	Hfo	Ge-P	FM IF, 60MHz	5k	AF 239 S	5g		AF 125...126, AF 200, AF 139, AF 239(S)
GF 126	Hfo	Ge-P	AM IF	5k	AF 239 S	5g		AF 125...126, AF 200, AF 139, AF 239(S)
GF 127	Hfo	Ge-P	AM Inp, 75MHz	5k	AF 239 S	5g		AF 125, AF 200, AF 139, AF 239(S)
GF 128	Hfo	Ge-P	AM/FM, 100MHz	5k	AF 239 S	5g		AF 124...125, AF 200, AF 139, AF 239(S)
GF 129	Hfo	Ge-P	AM Inp,Mx,Os, 75MHz	5k	AF 239 S	5g		AF 124...125, AF 200, AF 139, AF 239(S)
GF 130	Hfo	Ge-P	FM IF	5k	AF 239 S	5g		AF 125...126, AF 200, AF 139, AF 239(S)
GF 131	Hfo	Ge-P	FM Mx, 85MHz	5k	AF 239 S	5g		AF 124...125, AF 200, AF 139, AF 239(S)
GF 132	Hfo	Ge-P	FM Inp 85MHz	5k	AF 239 S	5g		AF 124, AF 200, AF 139, AF 239(S)
GF 134	Hfo	Ge-P	VHF, 180MHz	5k	AF 239 S	5g		AF 106, AF 109R, AF 239(S), AF 306
GF 135	Hfo	Ge-P	VHF, 150MHz	5g	AF 239 S	5g		AF 106, AF 109R, AF 239(S), AF 306
GF 136	Hfo	Ge-P	VHF, 150MHz	5g	AF 239 S	5g		AF 106, AF 109R, AF 239(S), AF 306
GF 137	Hfo	Ge-P	VHF, 180MHz	5g	AF 239 S	5g		AF 106, AF 109R, AF 239(S), AF 306
GF 138	Hfo	Ge-P	VHF, 180MHz	5g	AF 239 S	5g		AF 106, AF 109R, AF 239(S), AF 306
GF 139	Hfo	Ge-P	AM Inp,Mx, FM IF	5k	AF 239 S	5g		AF 106, AF 109R, AF 200, AF 239(S)
GF 140	Hfo	Ge-P	VHF Inp,Mx,Os, 300MHz	2a	AF 239 S	5g		AF 139, AF 239(S)
GF 141	Hfo	Ge-P	VHF Inp,Mx,Os, 300MHz	2a	AF 239 S	5g		AF 139, AF 239(S)
GF 142	Hfo	Ge-P	VHF Inp,Mx,Os, 300MHz	2a	AF 239 S	5g		AF 139, AF 239(S)
GF 143	Hfo	Ge-P	VHF Inp,Mx,Os, 300MHz	2a	AF 239 S	5g		AF 139, AF 239(S)
GF 145	Hfo	Ge-P	UHF Inp,Mx,Os, >250MHz	5g	AF 239 S	5g		AF 139, AF 239(S)
GF 146	Hfo	Ge-P	UHF Inp,Mx,Os, >600MHz	5g	AF 239 S	5g		AF 139, AF 239(S)
GF 147	Hfo	Ge-P	UHF, >600MHz	5g	AF 239 S	5g		AF 139, AF 239(S)
GF 180	Hfo	Ge-P	HF	5k	AF 239 S	5g		AF 106, AF 109R, AF 200, AF 306
GF 181	Hfo	Ge-P	HF, 100MHz	5k	AF 239 S	5g		AF 106, AF 109R, AF 200, AF 306
GF 268		N-FET	=BF 245	7f	BF 245	7f		+BF 245
GF 501	Hfo	Ge-P	HF, 300MHz	2a	AF 239 S	5g		AF 139, AF 239(S)
GF 502	Hfo	Ge-P	HF, 300MHz	2a	AF 239 S	5g		AF 139, AF 239(S)
GF 503	Hfo	Ge-P	HF, 300MHz	2a	AF 239 S	5g		AF 139, AF 239(S)
GF 504	Hfo	Ge-P	HF, 300MHz	2a	AF 239 S	5g		AF 139, AF 239(S)
GF 505	Hfo	Ge-P	HF, 170MHz	5g	AF 239 S	5g		AF 106, AF 109R, AF 239(S), AF 306
GF 506	Hfo	Ge-P	HF, 170MHz	5g	AF 239 S	5g		AF 106, AF 109R, AF 239(S), AF 306

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
GF 507	Hfo	Ge-P	HF, 250MHz	5g	AF 239 S	5g	AF 106, AF 109R, AF 239(S), AF 306	
GF 515	Hfo	Ge-P	HF, 60MHz	5k	AF 239 S	5g	AF 124...127, AF 200, AF 139, AF 239(S)	
GF 516	Hfo	Ge-P	HF, 60MHz	5k	AF 239 S	5g	AF 124...127, AF 200, AF 139, AF 239(S)	
GF 517	Hfo	Ge-P	HF, 50MHz	5k	AF 239 S	5g	AF 124...127, AF 200, AF 139, AF 239(S)	
GF 522		N-FET	=BF 245	7f	BF 245	7f	=BF 245	
GF 757		Si-N	=BF 757		BF 759	13h	=BF 757	
GF 758		Si-N	=BF 758		BF 759	13h	=BF 758	
GF 759		Si-N	=BF 759		BF 759	13h	=BF 759	
GF 760		Si-P	=BF 760		BF 762	13h	=BF 760	
GF 761		Si-P	=BF 761		BF 762	13h	=BF 761	
GF 762		Si-P	=BF 762		BF 762	13h	=BF 762	
GFT 20 A6	Hit	GTO-Thy	600V, 10A=(Tc=60°C), Igt/Ih=100/200mA, tqg=7µs	22a	TO-66		-	
GFT 20 B12	Hit	GTO-Thy	=GFT 20A6: 1200V, 7A=(Tc=60°C), tqg=6µs	22a	TO-66		-	
GFT 50 A6	Hit	GTO-Thy	600V, 20A=(Tc=60°C), Igt/Ih=300/600mA, tqg=7µs	23a	TO-3		-	
GFT 50 B12	Hit	GTO-Thy	=GFT 50A6: 1200V, 18A=(Tc=60°C), tqg=6µs	23a	TO-3		-	
GG...GL								
GG		Si-P	=2SA1369-G (SMD-Marking)	39	SOT-89		=2SA1369	
GG		Si-Di	=BAW 79C (SMD-Marking)	39	SOT-89		=BAW 79C	
GG		Si-P	=BF 579R (SMD-Marking)	35	SOT-23		=BF 579R	
GG		Si-N	=BFR 93P (SMD-Marking)	35	SOT-23		=BFR 93P	
GH		Si-P	=2SA1369-H (SMD-Marking)	39	SOT-89		=2SA1369	
GH		Si-Di	=BAW 79D (SMD-Marking)	39	SOT-89		=BAW 79D	
GH 1 E,F	Sak	Si-Di	Rr, 1300...1500V, 1A, Uf<1,05V(1A), <6µs E=1300V, F=1500V	31a	SOD-57	BY 228	31a	BY 228, BY 448, DM 513, EM 516, GP 10W
GH 3 E,F	Sak	Si-Di	Rr, 1300...1500V, 1.5A, Uf<1,2V(4A), <10µs E=1300V, F=1500V	31a	SOD-64	BY 228	31a	BY 228, BY 448, BY 350/...
GI 1-1200	Gie	Si-Di	Rr, 1200V, 1A, Uf<1,1V(1A), <1µs	31a	SOD-57	BY 133	31a	BY133, BY350/1300, CH 3E, EM 513, GP 100
GI 1-1400		Si-Di	=GI 1-1200: 1400V	31a	SOD-57	BY 228	31a	BY 350/1500, CH 3E, EM 516, GP 10V
GI 1-1600		Si-Di	=GI 1-1200: 1600V	31a	SOD-57			DM 513, DM 516, EM 516, GP 10Y
GI 250-1	Gie	Si-Di	kV-Rr, 1000V, 0,25A, Uf<3,5V(0,25A), 2µs	31a	DO-41	BA 159	31a	BA 159, BY 203/12, BY 204/10, MR 250-1
GI 250-2		Si-Di	=GI 250-1: 2000V	31a	DO-41	BY 203/20	31a	BY 203/20, GP 02-20, MR 250-2
GI 250-3		Si-Di	=GI 250-1: 3000V	31a	DO-41			GP 02-30, MR 250-3
GI 250-4		Si-Di	=GI 250-1: 4000V	31a	DO-41			GP 02-40, MR 250-4
GI 500	Gie	Si-Di	Rr, 50V, 3A, Uf<1,1V(9,4A), 2,5µs	31a	DO-27A	BY 255	31a	BY 251, G3A, GP 30A, MR 500, 1N5400, ++
GI 501	Gie	Si-Di	=GI 500: 100V	31a	DO-27A	BY 255	31a	BY 251, G3B, GP 30B, MR 501, 1N5401, ++
GI 502	Gie	Si-Di	=GI 500: 200V	31a	DO-27A	BY 255	31a	BY 251, G3D, GP 30D, MR 502, 1N5402, ++
GI 504	Gie	Si-Di	=GI 500: 400V	31a	DO-27A	BY 255	31a	BY 252, G3G, GP 30G, MR 504, 1N5404, ++
GI 506	Gie	Si-Di	=GI 500: 600V	31a	DO-27A	BY 255	31a	BY 253, G3J, GP 30J, MR 506, 1N5406, ++
GI 508	Gie	Si-Di	=GI 500: 800V	31a	DO-27A	BY 255	31a	BY 254, G3K, GP 30K, MR 508, 1N5407, ++
GI 510	Gie	Si-Di	=GI 500: 1000V	31a	DO-27A	BY 255	31a	BY 255, G3M, GP 30M, MR 510, 1N5408, ++
GI 750	Gie	Si-Di	Rr, 50V, 6A, Uf<0,9V(6A)	31a	(9x9mm0)	BY 500/800	31a	BY 214/50, BY 500/100, MR 750
GI 751	Gie	Si-Di	=MR 750: 100V	31a	(9x9mm0)	BY 500/800	31a	BY 214/100, BY 500/100, MR 751
GI 752	Gie	Si-Di	=MR 750: 200V	31a	(9x9mm0)	BY 500/800	31a	BY 214/200, BY 500/200, MR 752
GI 754	Gie	Si-Di	=MR 750: 400V	31a	(9x9mm0)	BY 500/800	31a	BY 214/400, BY 500/400, MR 754
GI 756	Gie	Si-Di	=MR 750: 600V	31a	(9x9mm0)	BY 500/800	31a	BY 214/600, BY 500/600, MR 756
GI 758	Gie	Si-Di	=MR 750: 800V	31a	(9x9mm0)	BY 500/800	31a	BY 214/800, BY 500/800, MR 758
GI 810	Gie	Si-Di	FRr, 50V, 1A, Uf<1,1V(1A), <750ns	31a	DO-15	BYD 33 M	31a	BYD 33D, BYT 52A, RGP 10A, MR 810, ++
GI 811	Gie	Si-Di	=GI 810: 100V	31a	DO-15	BYD 33 M	31a	BYD 33D, BYT 52B, RGP 10B, MR 811, ++
GI 812	Gie	Si-Di	=GI 810: 200V	31a	DO-15	BYD 33 M	31a	BYD 33D, BYT 52D, RGP 10D, MR 812, ++
GI 814	Gie	Si-Di	=GI 810: 400V	31a	DO-15	BYD 33 M	31a	BYD 33G, BYT 52G, RGP 10G, MR 814, ++
GI 816	Gie	Si-Di	=GI 810: 600V	31a	DO-15	BYD 33 M	31a	BYD 33J, BYT 52J, RGP 10J, MR 816, ++
GI 817	Gie	Si-Di	=GI 810: 800V	31a	DO-15	BYD 33 M	31a	BYD 33K, BYT 52K, RGP 10K, MR 817, ++
GI 818	Gie	Si-Di	=GI 810: 1000V	31a	DO-15	BYD 33 M	31a	BYD 33M, BYT 52M, RGP 10M, MR 818, ++
GI 820	Gie	Si-Di	FRr, 50V, 5A, Uf<1V(5A), <200ns	31a	(9x9mm0)	BY 500/800	31a	BY 500/100, EGP 50A, MR 820
GI 821	Gie	Si-Di	=GI 820: 100V	31a	(9x9mm0)	BY 500/800	31a	BY 500/100, EGP 50B, MR 821
GI 822	Gie	Si-Di	=GI 820: 200V	31a	(9x9mm0)	BY 500/800	31a	BY 500/200, EGP 50D, MR 822
GI 824	Gie	Si-Di	=GI 820: 400V	31a	(9x9mm0)	BY 500/800	31a	BY 500/400, EGP 50G, MR 824 ⁴
GI 826	Gie	Si-Di	=GI 820: 600V	31a	(9x9mm0)	BY 500/800	31a	BY 500/600, MR 826, (BY 229/600, ++) ⁴
GI 850	Gie	Si-Di	FRr, 50V, 3A, Uf=1,25V(3A), <200ns	31a	DO-27A	BYW 95 C	31a	BYW 95A, BYW 72, RGP 30A, MR 850
GI 851	Gie	Si-Di	=GI 850: 100V	31a	DO-27A	BYW 95 C	31a	BYW 95A, BYW 72, RGP 30B, MR 851
GI 852	Gie	Si-Di	=GI 850: 200V	31a	DO-27A	BYW 95 C	31a	BYW 95A, BYW 72, RGP 30D, MR 852
GI 854	Gie	Si-Di	=GI 850: 400V	31a	DO-27A	BYW 95 C	31a	BYW 95B, BYW 74, RGP 30G, MR 854
GI 856	Gie	Si-Di	=GI 850: 600V	31a	DO-27A	BYW 95 C	31a	BYW 95C, BYW 76, RGP 30J, MR 856
GI 910	Gie	Si-Di	FRr, 50V, 3A, Uf=1,25V(3A), <750ns	31a	DO-27A	BYW 95 C	31a	BYW 95A, BYW 72, RGP 30A, MR 850
GI 911	Gie	Si-Di	=GI 910: 100V	31a	DO-27A	BYW 95 C	31a	BYW 95A, BYW 72, RGP 30B, MR 851
GI 912	Gie	Si-Di	=GI 910: 200V	31a	DO-27	BYW 95 C	31a	BYW 95A, BYW 72, RGP 30D, MR 852
GI 914	Gie	Si-Di	=GI 910: 400V	31a	DO-27A	BYW 95 C	31a	BYW 95B, BYW 74, RGP 30G, MR 854
GI 916	Gie	Si-Di	=GI 910: 600V	31a	DO-27A	BYW 95 C	31a	BYW 95C, BYW 76, RGP 30J, MR 856
GI 917	Gie	Si-Di	=GI 910: 800V	31a	DO-27A	BYW 95 C	31a	BY 399, BYW 96D, BYT 77, RGP 30K
GI 1001	Gie	Si-Di	FRr, 50V, 1A, Uf<0,975V(1A), <25ns	31a	SOD-57	BYV 27/200	31a	BYV 26B, EGP 10A, FE 1A
GI 1002	Gie	Si-Di	=GI 1001: 100V	31a	SOD-57	BYV 27/200	31a	BYV 26B, EGP 10B, FE 1B
GI 1003	Gie	Si-Di	=GI 1001: 150V	31a	SOD-57	BYV 27/200	31a	BYV 26B, EGP 10C, FE 1C
GI 1004	Gie	Si-Di	=GI 1001: 200V, <40ns	31a	SOD-57	BYV 27/200	31a	BYV 26B, EGP 10D, FE 1D
GI 1101	Gie	Si-Di	FRr, 50V, 2,4A, 0,975V(2A), <25ns	31a	SOD-57	BYV 28/200	31a	BYV 28/50, EGP 30A, FE 3A
GI 1102	Gie	Si-Di	FRr, 100V, 2,4A, Uf<0,975V(2A), <25ns	31a	SOD-57	BYV 28/200	31a	BYV 28/100, EGP 30B, FE 3B
GI 1103	Gie	Si-Di	FRr, 150V, 2,4A, Uf<0,975V(2A), <25ns	31a	SOD-57	BYV 28/200	31a	BYV 28/150, EGP 30C, FE 3C
GI 1104	Gie	Si-Di	FRr, 200V, 2A, Uf<1,25V(2A), <50ns	31a	SOD-57	BYV 28/200	31a	BYV 28/200, EGP 30D, FE 3D
GI 1301	Gie	Si-Di	FRr, 50V, 6A, 0,925V(6A), <30ns	31a	SOD-64			BYV 61, FE 6A, (BYT 08/200, RGP 80A, ++) ⁴
GI 1302	Gie	Si-Di	FRr, 100V, 6A, Uf<0,925V(6A), <30ns	31a	SOD-64			BYV 62, FE 6B, (BYT 08/200, RGP 80B, ++) ⁴
GI 1303	Gie	Si-Di	FRr, 150V, 6A, Uf<0,925V(6A), <30ns	31a	SOD-64			BYV 63, FE 6C, (BYT 08/200, RGP 80C, ++) ⁴
GI 1304	Gie	Si-Di	FRr, 200V, 5A, Uf<1,25V(6A), <50ns	31a	SOD-64			FE 6D, (BYT 08/200, RGP 80D, ++) ⁴
GI 1401	Gie	Si-Di	P FRr, 50V, 8A(Tc=125°), Uf<0,975V(8A), <35ns	17k	TO-220			BYP 51-50, BYW 29/50, BYW 80/50, FE 8A
GI 1402	Gie	Si-Di	=GI 1401: 100A	17k	TO-220			BYP 51-100, BYW 29/100, BYW80/100, FE 8B
GI 1403	Gie	Si-Di	=GI 1401: 150A	17k	TO-220			BYP 51-150, BYW 29/150, BYW80/150, FE 8C
GI 1404	Gie	Si-Di	=GI 1401: 200A	17k	TO-220			BYP 51-200, BYW 29/200, BYW80/200, FE 8D
GI 1401R...1404R		Si-Di	=GI 1401...1404:	17m	TO-220			-
GI 2401	Gie	Si-Di	Dual, FRr, 50V, 16A(Tc=125°), Uf<0,975V(8A), <35ns	17e	TO-220			BYV 32/50, BYV 79/50, FE 16A, MUR 1605CT
GI 2402	Gie	Si-Di	=GI 2401: 100V	17e	TO-220			BYV32/100, BYV79/100, FE 16B, MUR 1610CT
GI 2403	Gie	Si-Di	=GI 2401: 150V	17e	TO-220			BYV32/150, BYV79/150, FE 16C, MUR 1615CT
GI 2404	Gie	Si-Di	=GI 2401: 200V	17e	TO-220			BYV32/200, BYV79/200, FE 16D, MUR 1620CT
GI 2401R...2404R		Si-Di	=GI 2401...2404:	17h	TO-220			BYV 32N/..., FE 16...N
GI 5823	Gie	Si-Di	Schottky, 20V, 5A, Uf<0,45V(5A), (=1N5823)	31a	DO-27A			SB 520, =1N5823

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
GI 5824	Gie	Si-Di	=GI 5823: 30V, (=1N5824)	31a			SB 530, =1N5824	
GI 5825	Gie	Si-Di	=GI 5823: 40V, (=1N5825)	31a			SB 540, 1N5825	
GIA		Si-N-Darl	=2SC3957-GIA (SMD-Marking)	44			*2SC3957	
GIB		Si-N-Darl	=2SC3957-GIB (SMD-Marking)	44			*2SC3957	
GJ 2		N-FET	=2SK968-2 (SMD-Marking)	35			*2SK968	
GJ 3		N-FET	=2SK968-3 (SMD-Marking)	35			*2SK968	
GJ 4		N-FET	=2SK968-4 (SMD-Marking)	35			*2SK968	
GJ 5		N-FET	=2SK968-5 (SMD-Marking)	35			*2SK968	
GK		Si-N	=2SD1615-GK (SMD-Marking)	39			*2SD1615	
GK		Z-Di	=SM 6T 150 (SMD-Marking)	71a(6x4mm)	SOD-6		*SM 6T....	
GL		Si-P	=2SA1496 (SMD-Marking)	35			*2SA1496	
GL		Si-N	=2SD1615-GL (SMD-Marking)	39			*2SD1615	
GL		Z-Di	=SM 6T 150A (SMD-Marking)	71a(6x4mm)	SOD-6		*SM 6T....	
GL 27 A...M	Gie	Si-Di	=BYM 30/....				*BYM 30/...	
GL 34 A...M	Gie	Si-Di	=BYM 05/....				*BYM 05/...	
GL 41 A...M	Gie	Si-Di	=BYM 10/....				*BYM 10/...	
GL 317		Z-IC	+1.7...37V, 0.01...1.5A, 20W, -20...+100°	17l	TO-220	LM 317 T	17l	... 117... 217... 317...
GL 7805		Z-IC	=LM 7805	17b	TO-220	=LM 7805		*LM 7805
GL 7812		Z-IC	=LM 7812	17b	TO-220	=LM 7812		*LM 7812
GLC 555		LIH-IC	=NE 555CH,CM: SMD					*NE 555...
GLC 556		LIH-IC	=NE 556CH,CM: SMD					*NE 556...
GLC 4558		OP-IC	SMD, Dual, Serie 158, ±18V, 0...+70°					... 258... 358... 1458... 4558...
GLC 4559		OP-IC	=GLC 4558: io-noise					... 258... 358... 1458... 4559...
GLL 4735...4763	Gie	Si-Di	=1N4735...4763: SMD	72a(5mm)	(MELF)			
GLT 12	Tho	Z-Di	=BZW 25/12:	32	DO-4			*BZW 25/12
GLT 24	Tho	Z-Di	=BZW 25/24:	32	DO-4			*BZW 25/24
GLT 47	Tho	Z-Di	=BZW 25/47:	32	DO-4			*BZW 25/47
GLT 120	Tho	Z-Di	=BZW 25/120:	32	DO-4			*BZW 25/120
GM...GO								
GM		Si-N	=2SD1615-GM (SMD-Marking)	39	SOT-89			*2SD1615
GM-1 A...Z	Sak	Si-Di	Rr, Uni, 200...1000V, 1,3A, Uf<1,2V(1A) A=600V, B=800V, C=1000V, Z=200V	31a	SOD-57	BY 255	31a	BY 226...227, BY 251...255, 1N5391...99, ++
GM 3 A...Z	Sak	Si-Di	Rr, Uni, 100...1000V, 2,7A, Uf<1,2V(3A) A=600V, B=800V, C=1000V, Y=100V, Z=200V	31a	SOD-64	BY 255	31a	BY 251...255, GP 30B...M, 1N5401...08, ++
GM 30 A...M	Gie	Si-Di	Dual, 50...1000V, 30A(Tc=100°), Uf<1,1V(15A), 5µs A=50, B=100, D=200, G=400, J=600, K=800, M=1000V	23f	TO-3			BYV 72/..., BYW 99P/..., RP 30AP...MP
GM 30 AD...MD		Si-Di	=GM 30A...M:	23s	TO-3			
GM 30 AN...MN		Si-Di	=GM 30A...M:	23n	TO-3			
GM 0290(A)	Tix	Ge-P	UHF Inp,Mx,Os, 750MHz	5g		AF 239 S	5g	AF 139, AF 239(S)
GM 0378(A)	Tix	Ge-P	VHF, 600MHz	5g		AF 239 S	5g	AF 139, AF 239(S)
GM 0656(A)	Tix	Ge-P	UHF Os	5g		AF 239 S	5g	AF 139, AF 239(S)
GM 0760	Tix	Ge-P	VHF Inp	5g		AF 239 S	5g	AF 106, AF 109R, AF 239(S), AF 306
GM 0761	Tix	Ge-P	VHF Mx	5g		AF 239 S	5g	AF 106, AF 109R, AF 239(S), AF 306
GM 62093		CMOS-IC	=KS 093					KS 093, M 093, MT 8812
GMA 01	Say	Si-Di	SS, 55/60V, 0,12/0,36V, Uf<0,65V(1,5mA), <4ns	31a	DO-35	1N4148	31a	BAW 62, BAW 76, BAX 95, 1N4148...49, ++
GMA 01 U	Say	Si-Di	=GMA 01: 100/105V	31a	DO-35	(1N4148)	31a	BAV 14
GMB 01(U)	Say	Si-Di	=GMA 01: 100/105V	31a	DO-34	=GMA 01(U)		=GMA 01(U)
GMJ 2955		Si-P	=BD 208	14h	TO-126			*BD 208
GMJ 3055		Si-N	=BD 207	14h	TO-126			*BD 207
GN 1 A3Q	Nec	Si-P+R	=AN 1A3Q: SMD	(GA1A3Q 35a(2mm)	SOT-323			DTA 113ZU
GN 1 A4M	Nec	Si-P+R	=AN 1A4M: SMD	(GA1A4M 35a(2mm)	SOT-323			DTA 114EU, 2SA1678
GN 1 A4P	Nec	Si-P+R	=AN 1A4P: SMD	(GA1A4P 35a(2mm)	SOT-323			DTA 114YU
GN 1 A4Z	Nec	Si-P+R	=AN 1A4Z: SMD	(GA1A4Z 35a(2mm)	SOT-323			DTA 114TU
GN 1 F4M	Nec	Si-P+R	=AN 1F4M: SMD	(GA1F4M 35a(2mm)	SOT-323			DTA 124EU, 2SA1677
GN 1 F4N	Nec	Si-P+R	=AN 1F4N: SMD	(GA1F4N 35a(2mm)	SOT-323			DTA 124XU
GN 1 F4Z	Nec	Si-P+R	=AN 1F4Z: SMD	(GA1F4Z 35a(2mm)	SOT-323			DTA 124TU
GN 1 L3M	Nec	Si-P+R	=AN 1L3M: SMD	(GA1L3M 35a(2mm)	SOT-323			DTA 143EU
GN 1 L3N	Nec	Si-P+R	=AN 1L3N: SMD	(GA1L3N 35a(2mm)	SOT-323			DTA 143XU
GN 1 L3Z	Nec	Si-P+R	=AN 1L3Z: SMD	(GA1L3Z 35a(2mm)	SOT-323			DTA 143TU
GN 1 L4L	Nec	Si-P+R	=AN 1L4L: SMD	(GA1L4L 35a(2mm)	SOT-323			DTA 143WU
GN 1 L4M	Nec	Si-P+R	=AN 1L4M: SMD	(GA1L4M 35a(2mm)	SOT-323			DTA 144EU, 2SA1676
GN 1 L4Z	Nec	Si-P+R	=AN 1L4Z: SMD	(GA1L4Z 35a(2mm)	SOT-323			DTA 144TU
GN 1010...8062	Mat	GaAs-FET	MMIC, UHF MES-FET Arrays					
GO		Si-P	=2SA2883-O (SMD-Marking)	39	SOT-89			*2SA2883
GO		Si-N	=2SC2996-O (SMD-Marking)	35	SOT-23			*2SC2996
GO		Si-N	=KTC4375-O (SMD-Marking)	39	SOT-89			*KTC 4375
GP...GR								
GP		Si-N	=2SD1615A-GP (SMD-Marking)	39	SOT-89			*2SD1615A
GP 02-20...40	Gie	Si-Di	kV-Rr, 2...4kV, 0,25A, Uf<3V(1A), 2µs	31a	DO-41			MR 250-2...-5, 1N1732A...1734A
GP 08 A...J	Gie	Si-Di	Rr, 50...600V, 0,8A, Uf<1,3V(0,8A), 1µs	31a	DO-41	1N4007	31a	BY 126...127, BY 133...135, 1N4001...07, ++
GP 10 A...M	Gie	Si-Di	Rr, 50...1000V, 1A, Uf<1,1V(1A), 2µs A=50, B=100, D=200, G=400, J=600, K=800, M=1000V	31a	DO-41	1N4007	31a	BY 126...127, BY 133...135, 1N4001...07, ++
GP 10 N...Y		Si-Di	=GP 10A...M: 1100...1600V, Uf<1,3V(1A) N=1100, Q=1200, T=1300, V=1400, W=1500, Y=1600V	31a	DO-41	BY 228	31a	BY 350/1500, GH 3F, DM 513, EM 516, ++
GP 15 A...M	Gie	Si-Di	Rr, 50...1000V, 1,5A, Uf<1,1V(1,5A), 2µs A=50, B=100, D=200, G=400, J=600, K=800, M=1000V	31a	DO-15	BYD 33 M	31a	BY 226...227, BY 251...255, 1N5391...99, ++
GP 20 A...M	Gie	Si-Di	Rr, 50...1000V, 2A, Uf<1,2V(2A), 2,5µs	31a	DO-27	BY 255	31a	BY 251...255, MR 500...510, 1N5400...08, ++
GP 30 A...M	Gie	Si-Di	Rr, 50...1000V, 3A, Uf<1,2V(3A), 3µs	31a	DO-27A	BY 255	31a	BY 251...255, MR 500...510, 1N5400...08, ++
GP 80 A...M	Gie	Si-Di	P Rr, 50...1000V, 8A(Tc=100°), Uf<1V(8A), 5µs	17k	TO-220	BY 359/1500	17k	BY 239/..., BY 359/..., RGP 80...
GP 140		Si-N-Darl	=BDW 83C	18j	TO-3P	BDW 83 C	18j	=BDW 83C
GP 145		Si-P-Darl	=BDW 84C	18j	TO-3P	BDW 84 C	18j	=BDW 84C
GPP 10 A...M	Sym	Si-Di	=GP 10A...M	31a	DO-41	*GP 10A...M		*GP 10A...M
GPP 15 A...M	Sym	Si-Di	=GP 15A...M	31a	DO-15	*GP 15A...M		*GP 15A...M
GPP 20 A...M	Sym	Si-Di	=GP 20A...M	31a	DO-15	*GP 20A...M		*GP 20A...M
GPP 30 A...M	Sym	Si-Di	=GP 30A...M	31a	DO-27A	*GP 30A...M		*GP 30A...M
GPP 60 A...M	Sym	Si-Di	Rr, 50...1000V, 6A, Uf<1,1V(6A) A=50, B=100, D=200, G=400, J=600, K=800, M=1000V	31a	(9x9mm0)			BY 214/..., MR 750...760
GPS-....		Si-N/P	=MPS-....			*MPS-....		*MPS-....
GPU 2243	Itt	NMOS-IC	CTV, Digital SECAM Chroma Processor	40-DIP				
GO		Si-N	=2SD1615A-GO (SMD-Marking)	39	SOT-89			*2SD1615A
GR		Si-P	=2SA1455K-R (SMD-Marking)	35	SOT-23			*2SA1455K

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International	
GR		Si-N	=2SC2996-R (SMD-Marking)	35		SOT-23	=2SC2996	
GS								
GS		Si-P	=2SA1455K-S (SMD-Marking)	35		SOT-23	=2SA1455K	
GS 100(B...D)	Hfo	Ge-P	S, 25V, 0.05A, 0.03W, <1500/-ns	2a		AC 151	2a	AC 122, AC 125...126, AC 151, ASY 26...27
GS 109(B...D)	Hfo	Ge-P	S, 20V, 0.05A, 0.083W, <1500/-ns	2a		AC 151	2a	AC 122, AC 125...126, AC 151, ASY 26...27
GS 110	Hfo	Ge-P	S, 20V, 0.3A, 0.083W, <1500/-ns	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188, ASY 76...77
GS 111(B...E)	Hfo	Ge-P	S, 20V, 0.2A, 0.083W, <1200/1500ns	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188, ASY 76...77
GS 112(B...E)	Hfo	Ge-P	=GS 111: <900/1500ns	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188, ASY 76...77
GS 121(B...D)	Hfo	Ge-P	S, 20V, 0.1A, 0.15W, <10µs	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188, ASY 76...77
GS 122	Hfo	Ge-P	=GS 121: 30V	2a		AC 188 K	3a	AC 128, AC 152...153, AC 188, ASY 76...77
GS 9010...9022		Si-N/P	=CS 9010...9022			=CS 9010-9022		
GSA 15 B...G	Say	Si-Di	Rr, Uni, 100...600V, 1.5A, Uf<1V(1.5A)	31a	SOD-57	BYD 33 M	31a	BY 226...227, BY 251...255, 1N5391...99, ++
GSA 17 B...E	Say	Si-Di	Rr, Uni, 100...400V, 1.7A, Uf<1.05V(1.7A)	31a	DO-15	BY 255	31a	BY 251...255, MR 500...510, 1N5400...08, ++
GSA 26 B...E	Say	Si-Di	Rr, Uni, 100...400V, 2.6A, Uf<1.05V(2.6A)	31a	DO-15	BY 255	31a	BY 251...255, MR 500...510, 1N5400...08, ++
GSA 30 B...J	Say	Si-Di	Rr, Uni, 100...800V, 3A, Uf<1V(3A)	31a	SOD-64	BY 255	31a	BY 251...255, MR 500...510, 1N5400...08, ++
GS-H9012		Si-P	=SS 9012			=SS 9012		=SS 9012
GS-H9032		Si-P	=CS 9012			BC 327	7a	
GS-H9033		Si-N	=CS 9013			BC 337	7a	
GT...GZ								
GT		Si-N	=2SC4168 (SMD-Marking)	35		SOT-23		=2SC4168
GT		Si-N	=2SC4443 (SMD-Marking)	35(2mm)		SOT-323		=2SC4443
GT		Z-Di	=SM 6T 200 (SMD-Marking)	71a(6x4mm)		SOD-6		=SM 6T....
GT 8 J101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 600/20V, 8/16A, 30W			17(GCE) TO-220 Iso		
GT 8 J102	Tos	MOS-N-IGBT-e	=GT 8J101: 50W			30(GCE) (TO-220MF)		
GT 8 N101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 1000/20V, 8/16A, 100W			18(GCEC) TO-3P		BUP 302
GT 8 Q101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 1200/20V, 8/16A, 100W			18(GCEC) TO-3P		
GT 10 G101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 400/25V, 10/130A, 30W			17(GCE) TO-220 Iso		
GT 10 G102	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 400/20V, 10/130A, 30W			17(GCE) TO-220 Iso		
GT 15 G101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 400/25V, 15/170A, 40W			17(GCE) TO-220 Iso		
GT 15 J101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 600/20V, 15/30A, 100W			18(GCEC) TO-3P		
GT 15 J102	Tos	MOS-N-IGBT-e	=GT 15J101: 35W			17(GCE) TO-220 Iso		
GT 15 J103	Tos	MOS-N-IGBT-e	=GT 15J101: 70W			30(GCE) (TO-220MF)		
GT 15 N101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 1000/20V, 15/30A, 150W			18(GCEC) TO-3P		BUP 303
GT 15 Q101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 1200/20V, 15/30A, 150W			18(GCEC) TO-3P		
GT 20 D101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 250/20V, 20/60A, 180W			77(GCEC) TOP-3L		
GT 20 D201	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 250/20V, 20/60A, 180W			77(GCEC) TOP-3L		
GT 20 G101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 400/25V, 20/130A, 60W			30(GCEC) (TO-220MF)		
GT 20 G102	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 400/25V, 20/130A, 60W			30(GCEC) (TO-220MF)		
GT 25 G101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 400/25V, 25/130A, 75W			30(GCEC) (TO-220MF)		
GT 25 G102	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 400/25V, 25/150A, 75W			30(GCEC) (TO-220MF)		
GT 25 J101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 600/20V, 25/50A, 150W			18(GCEC) TO-3P		
GT 25 Q101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 1200/20V, 25/50A, 200W			77(GCEC) TOP-3L		
GT 50 J101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 600/20V, 50/100A, 200W			77(GCEC) TOP-3L		
GT 50 M101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 900/25V, 50/100A, 80W			77(GCEC) TOP-3L		
GT 60 J101	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 600/20V, 60/120A, 200W			77(GCEC) TOP-3L		
GT 60 M102	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 900/25V, 60/120A, 200W			77(GCEC) TOP-3L		
GT 60 M103	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 900/25V, 60/120A, 200W			77(GCEC) TOP-3L		
GT 60 M104	Tos	MOS-N-IGBT-e	Iso-Gate bipolar Trans., 900/25V, 60/120A, 200W			77(GCEC) TOP-3L		
GT 322	Gdc,Usr	Ge-P	HF, >80MHz	5k		AF 239 S	5g	AF 139, AF 200, AF 239(S)
GT 328(A,B)	Gdc,Usr	Ge-P	VHF, >400MHz	5g		AF 239 S	5g	AF 139, AF 239(S)
GT 346(A,B)	Gdc,Usr	Ge-P	VHF/UHF, 600...700MHz	5g		AF 239 S	5g	AF 139, AF 239(S)
GU		Z-Di	=SM 6T 200A (SMD-Marking)	71a(6x4mm)		SOD-6		=SM 6T....
GU-1(A,B,Z)	Sak	Si-Di	Rr, 200...800V, 0.8A, Uf<1.4V(1A), <1µs GU-1: 400V, A=600V, B=800V, Z=200V	31a	SOD-57	BA 159	31a	BA157...159, BY204/..., BY208/..., BY268,++
GU-1 E	Sak	Si-Di	Rr, 1300V, 0.3A, Uf<3V(1A), <2µs	31a	SOD-57	BY 228	31a	BY 228, BY 231/1400, DM 513, GP 10V...Y
GU-1 F	Sak	Si-Di	=GU-1E: 1500V	31a	SOD-57	BY 228	31a	BY 228, BY 231/1500, DM 516, GP 10Y
GU-3(A,B,Z)	Sak	Si-Di	Frr, 200...800V, 1A, Uf<1.3V(1A), <500ns GU-3: 400V, A=600V, B=800V, Z=200V	31a	SOD-64	BYD 33 M	31a	BYT 52A...M, BYV 12...16, RG 1A...M, ++
GU-3 SY...SZ	Sak	Si-Di	Frr, SY=100, SZ=200V, 3A, Uf<1.2V(1A), <500ns	31a	SOD-64	BYW 95 C	31a	BYW 95A...C, BYW 96D...E, RG 3A...M, ++
GV		PIN-Di	=1SV249 (SMD-Marking)	35 (2mm)		SOT-323		=1SV249
GV		PIN-Di	=1SV251 (SMD-Marking)	35		SOT-23		=1SV251
GV		Z-Di	=SM 6T 220 (SMD-Marking)	71a(6x4mm)		SOD-6		=SM 6T....
GW		Z-Di	=SM 6T 220A (SMD-Marking)	71a(6x4mm)		SOD-6		=SM 6T....
GX		Si-N	=2SD2403-GX (SMD-Marking)	39		SOT-89		=2SD2403
GXB 10147 A	Sie	ECL-RAM-IC	128x1 Bit, <12ns, Ucc=-5.2V			16-DIC		
GXB 10149	Sie	ECL-PROM-IC	256x4 Bit, <20ns, Ucc=-5.2V			16-DIC		
GXB 100473	Sie	ECL-RAM-IC	64x4 Bit, <8ns, Ucc=-4.5V			24-FLP		
GXB 100474	Sie	ECL-RAM-IC	1024x4 Bit, <25ns, Ucc=-4.5V			24-FLP		
GY		Si-P	=2SA2883-Y (SMD-Marking)	39		SOT-89		=2SA2883
GY		Si-N	=2SC2996-Y (SMD-Marking)	35		SOT-23		=2SC2996
GY		Si-N	=2SC3689 (SMD-Marking)	35		SOT-23		=2SC3689
GY		Si-N	=2SC4413 (SMD-Marking)	35(2mm)		SOT-323		=2SC4413
GY		Si-N	=2SD2403-GY (SMD-Marking)	39		SOT-89		=2SD2403
GY		Si-N	=KTC4375-Y (SMD-Marking)	39		SOT-89		=KTC 4375
GZ		Si-N	=2SD2403-GZ (SMD-Marking)	39		SOT-89		=2SD2403
GZ		Si-N	=BFR 35AR (SMD-Marking)	35		SOT-23		=BFR 35AR
GZA 2.0...51(X,Y,Z)	Say	Z-Di	2.0...51V, 0.5W, X=-6...-1%, Y=+2.5%, Z=+1...+6%	31a	DO-35	Z-Diode ...V	31a	BZW 22/..., BZX 55/..., BZX 85/..., ZPD...+
GZB 2.0...36(B,C)	Say	Z-Di	2...36V, 1W, B=6%, C=0...+12%	31a	DO-41	Z-Diode ...V	31a	BZV 85/..., BZW 22/..., BZX 61/..., ZPY...+
GZB 1500 S1	Phi	LIN-IC	US FB Sender/Transmitter			24-DIP		
GZB 1504	Phi	LIN-IC	US FB Sender/Transmitter					
GZS 2.0...39(R...Z)	Say	Z-Di	2.0...39V, 0.4WR, -1...+2,X=-8...-4,Y=-5...0,Z=-2...+3%	31a	DO-35	Z-Diode ...V	31a	BZW 22/..., BZX 55/..., BZX 85/..., ZPD...+
H								
H 0		Si-N	=2SC4252 (SMD-Marking)	35(2mm)		SOT-323		=2SC4252
H 0		Si-N	=2SC4255 (SMD-Marking)	35		SOT-23		=2SC4255
H		Si-N	=2SC4446 (SMD-Marking)	35(2mm)		SOT-323		=2SC4446
H		GaAs-N-FET	=2SK1100 (Marking)	51		SOT-173		=2SK1100
H		GaAs-N-FET	=2SK1229 (Marking)	51		SOT-173		=2SK1229
H		C-Di	=HVU 354 (SMD-Marking)	71(1,7mm)		SOT-323		=HVU 354
H 1(p)		Si-P	=BCW 69 (SMD-Marking)	35		SOT-23		=BCW 69
H 1		Si-N	=BFS 46 (SMD-Marking)	35		SOT-23		=BFS 42

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
H 1		Si-P	=D71Y1.5T1 (SMD-Marking)	39	SOT-89		•D71Y1.5T1	
H 1		Si-Di	=HVM 187WK (SMD-Marking)	35	SOT-23		•HVM 187WK	
H10		Si-P	=KSA 2755-O (SMD-Marking)	35	SOT-23		•KSA 2755	
H10		Si-P	=KSA 2859-O (SMD-Marking)	35	SOT-23		•KSA 2859	
H1R		Si-P	=KSA 2755-R (SMD-Marking)	35	SOT-23		•KSA 2755	
H1Y		Si-P	=KSA 2755-Y (SMD-Marking)	35	SOT-23		•KSA 2755	
H1Y		Si-P	=KSA 2859-Y (SMD-Marking)	35	SOT-23		•KSA 2859	
H 2(p)		Si-P	=BCW 70 (SMD-Marking)	35	SOT-23		•BCW 70	
H 2		Si-N	=BFS 46A (SMD-Marking)	35	SOT-23		•BFS 42A	
H 2		Si-Di	=HVM 13 (SMD-Marking)	35	SOT-23		•HVM 13	
H20		Si-N	=KSC 2756-Y (SMD-Marking)	35	SOT-23		•KSC 2756	
H2R		Si-N	=KSC 2756-R (SMD-Marking)	35	SOT-23		•KSC 2756	
H2Y		Si-N	=KSC 2756-Y (SMD-Marking)	35	SOT-23		•KSC 2756	
H 3		Si-P	=2SA956-H3 (SMD-Marking)	35	SOT-23		•2SA956	
H 3(p)		Si-P	=BCW 89 (SMD-Marking)	35	SOT-23		•BCW 89	
H 3		Si-Di	=HVM 187S (SMD-Marking)	35	SOT-23		•HVM 187S	
H30		Si-N	=KSC 2757-O (SMD-Marking)	35	SOT-23		•KSC 2757	
H3R		Si-N	=KSC 2757-R (SMD-Marking)	35	SOT-23		•KSC 2757	
H3Y		Si-N	=KSC 2757-Y (SMD-Marking)	35	SOT-23		•KSC 2757	
H 4		Si-P	=2SA956-H4 (SMD-Marking)	35	SOT-23		•2SA956	
H 4		Si-N	=2SC3134-4 (SMD-Marking)	35	SOT-23		•2SC3134	
H 4		Si-P	=BCW 69R (SMD-Marking)	35	SOT-23		•BCW 69R	
H4Z		Si-N	=KSC 2758 (SMD-Marking)	35	SOT-23		•KSC 2758	
H 5		Si-P	=2SA956-H5 (SMD-Marking)	35	SOT-23		•2SA956	
H 5		Si-N	=2SC3134-5 (SMD-Marking)	35	SOT-23		•2SC3134	
H 5		Si-P	=BCW 70R (SMD-Marking)	35	SOT-23		•BCW 70R	
H 5		Si-Di	=HVM 14 (SMD-Marking)	35	SOT-23		•HVM 14	
H50		Si-N	=KSC 2223-O (SMD-Marking)	35	SOT-23		•KSC 2223	
H5R		Si-N	=KSC 2223-R (SMD-Marking)	35	SOT-23		•KSC 2223	
H5Y		Si-N	=KSC 2223-Y (SMD-Marking)	35	SOT-23		•KSC 2223	
H 6		Si-P	=2SA956-H6 (SMD-Marking)	35	SOT-23		•2SA956	
H 6		Si-N	=2SC3134-6 (SMD-Marking)	35	SOT-23		•2SC3134	
H 6		Si-P	=BCW 89R (SMD-Marking)	35	SOT-23		•BCW 89R	
H 6		Si-Di	=HVM 14S (SMD-Marking)	35	SOT-23		•HVM 14S	
H60		Si-N	=KSC 2759-O (SMD-Marking)	35	SOT-23		•KSC 2759	
H6R		Si-N	=KSC 2759-R (SMD-Marking)	35	SOT-23		•KSC 2759	
H6Y		Si-N	=KSC 2759-Y (SMD-Marking)	35	SOT-23		•KSC 2759	
H 7		Si-N	=2SC3134-7 (SMD-Marking)	35	SOT-23		•2SC3134	
H 7		Si-P	=BCF 70 (SMD-Marking)	35	SOT-23		•BCF 70	
H 6		Si-Di	=HVM 14SR (SMD-Marking)	35	SOT-23		•HVM 14SR	
H 8 D1010		Hybrid-IC	Vorverstärker/Pre-amplifier				-	
H 8 D1011		Hybrid-IC	Vorverstärker/Pre-amplifier				-	
H 8 D1029		Hybrid-IC	Vorverstärker/Pre-amplifier				-	
H 8 D1044		Hybrid-IC	Vorverstärker/Pre-amplifier				-	
H 8 D1063		Hybrid-IC	Vorverstärker/Pre-amplifier				-	
H 8 D1153		Hybrid-IC	Vorverstärker/Pre-amplifier				-	
H 8 Z		Si-N	=KSC 2734 (SMD-Marking)	35	SOT-23		•2SC2734	
H 9		Si-Di	=1SS344 (SMD-Marking)	35	SOT-23		•1SS344	
H 9 Z		Si-N	=KSC 3120 (SMD-Marking)	35	SOT-23		•2SC3120	
H 11		MOS-P-FET-e	=2SJ166 (SMD-Marking)	35	SOT-23		•2SJ166	
H 11		Si-P	=BCX 71G (SMD-Marking)	35	SOT-23		•BCX 71G	
H 12		MOS-P-FET-e	=2SJ185 (SMD-Marking)	35	SOT-23		•2SJ185	
H 12		Si-P	=BCX 71H (SMD-Marking)	35	SOT-23		•BCX 71H	
H 13		MOS-P-FET-e	=2SJ202 (SMD-Marking)	35(2mm)	SOT-323		•2SJ202	
H 13		Si-P	=BCX 71J (SMD-Marking)	35	SOT-23		•BCX 71J	
H 14		MOS-P-FET-e	=2SJ203 (SMD-Marking)	35	SOT-23		•2SJ203	
H 14		Si-P	=BCX 71K (SMD-Marking)	35	SOT-23		•BCX 71K	
H 15		MOS-P-FET-e	=2SJ204 (SMD-Marking)	35	SOT-23		•2SJ204	
H 16		MOS-P-FET-e	=2SJ210 (SMD-Marking)	35	SOT-23		•2SJ210	
H 17		MOS-P-FET-e	=2SJ209 (SMD-Marking)	35	SOT-23		•2SJ209	
H 18		MOS-P-FET-e	=2SJ211 (SMD-Marking)	35	SOT-23		•2SJ211	
H 31		Si-P	=BCW 89R (SMD-Marking)	35	SOT-23		•BCW 89R	
H 32		Si-Di	=1N4148	31a	1N4148	31a	•1N4148	
H 71		Si-P	=BCF 70R (SMD-Marking)	35	SOT-23		•BCF 70R	
H 580	Sgs	LIN-IC	=SAS 580	18-DIP	SAS 580	18-DIP	SAS 580	
H 590	Sgs	LIN-IC	=SAS 590	18-DIP	SAS 590	18-DIP	SAS 590	
H 629	Sgs	MOS-IC	Orgelgatter, Gates f. Electronic Organ, 1x12	14-DIP			-	
H 770	Sgs	LIN-IC	=SN 29770	16-DIP			SN 29770	
H 771	Sgs	LIN-IC	=SN 29771	16-DIP			SN 29771	
H 772	Sgs	LIN-IC	=SN 29772	16-DIP			SN 29772	
H 773	Sgs	LIN-IC	=SN 29773	16-DIP			SN 29773	
H 4249		Si-N		17j	TO-220	BUT 56 A	17j	
HA								
HA		Si-N	=2SC2804 (Marking)	25	SOT-103		•2SC2804	
HA		Si-N	=2SC3119 (SMD-Marking)	35	SOT-23		•2SC3119	
HA		Si-N	=2SD1464-HA (SMD-Marking)	39	SOT-89		•2SD1464	
HA		Si-P	=BSS 25 (SMD-Marking)	35	SOT-23		•BSS 25	
HA		GaAs-N-FET-d	=CFY 65-12 (Marking)	51			•CFY 55	
HA		Si-P	=µPA601T (SMD-Marking)	46	SOT-163		•µPA601T	
HA 1-2650	Has	OP-IC	Dual, Serie 158, ±20V, -55...+125°	14-DIC			... 158... 1558... 2904...	
HA 1-2655	Has	OP-IC	Dual, Serie 158, ±20V, 0...+75°	14-DIC			... 158... 258... 358... 1458...	
HA 3-4741-5	Ray	OP-IC	Quad, ±20V, 0...+75°	14-DIP			-	
HA 178L02(P).A(PA)	Hit	Z-IC	+2V, 0.15A, ±8%, A=±5%	7b	TO-92L		... 78L02(TO-92)	
HA 178L05(P).A(PA)	Hit	Z-IC	+5V, 0.15A, ±8%, A=±5%	7b	TO-92L	78L05/TO-92	7b	... 78L05(TO-92)
HA 178L06(P).A(PA)	Hit	Z-IC	+6V, 0.15A, ±8%, A=±5%	7b	TO-92L		... 78L06(TO-92)	
HA 178L08(P).A(PA)	Hit	Z-IC	+8V, 0.15A, ±8%, A=±5%	7b	TO-92L	78L08/TO-92	7b	... 78L08(TO-92)
HA 178L09(P).A(PA)	Hit	Z-IC	+9V, 0.15A, ±8%, A=±5%	7b	TO-92L		... 78L09(TO-92)	
HA 178L10(P).A(PA)	Hit	Z-IC	+10V, 0.15A, ±8%, A=±5%	7b	TO-92L		... 78L10(TO-92)	
HA 178L12(P).A(PA)	Hit	Z-IC	+12V, 0.15A, ±8%, A=±5%	7b	TO-92L	78L12/TO-92	7b	... 78L12(TO-92)
HA 178L15(P).A(PA)	Hit	Z-IC	+15V, 0.15A, ±8%, A=±5%	7b	TO-92L	78L15/TO-92	7b	... 78L15(TO-92)
HA 178L56(P).A(PA)	Hit	Z-IC	+5,6V, 0.15A, ±8%, A=±5%	7b	TO-92L		... 78L56(TO-92)	
HA 178 L02...L15UA	Hit	Z-IC	=HA 178L02...L15: SMD	39b	SOT-89		M 5278LxxM, TA 78LxxF, ...78Lxx... (SOT-89)	

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
HA 178 M05(P,PJ)...	Hit	Z-IC	+5V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7805/TO-220	17b ... 78M05... (TO-220)
HA 178 M06(P,PJ)...	Hit	Z-IC	+6V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7806/TO-220	17b ... 78M06... (TO-220)
HA 178 M07(P,PJ)...	Hit	Z-IC	+7V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220		... 78M07... (TO-220)
HA 178 M08(P,PJ)...	Hit	Z-IC	+8V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7808/TO-220	17b ... 78M08... (TO-220)
HA 178 M09(P,PJ)...	Hit	Z-IC	+9V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7809/TO-220	17b ... 78M09... (TO-220)
HA 178 M12(P,PJ)...	Hit	Z-IC	+12V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7812/TO-220	17b ... 78M12... (TO-220)
HA 178 M15(P,PJ)...	Hit	Z-IC	+15V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7815/TO-220	17b ... 78M15... (TO-220)
HA 178 M18(P,PJ)...	Hit	Z-IC	+18V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7818/TO-220	17b ... 78M18... (TO-220)
HA 178 M20(P,PJ)...	Hit	Z-IC	+20V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7820/TO-220	17b ... 78M20... (TO-220)
HA 178 M24(P,PJ)...	Hit	Z-IC	+24V, 0.5A, ±4%, A=±2%, B=±3%, C=±2/-4%	17b	TO-220	7824/TO-220	17b ... 78M24... (TO-220)
HA 178 MxxFM,FMP	Hit	Z-IC	=HA 178 M05...M24(P,PJ): Iso	17b	TO-220 Iso		... 78Mxx... (TO-220 Iso)
HA 179L05(P),A(PA)	Hit	Z-IC	-5V, 0.15A, ±4%, A=±2%	7a	TO-92L	79L05/TO-92	7a ... 79L05(TO-92)
HA 179L06(P),A(PA)	Hit	Z-IC	-6V, 0.15A, ±4%, A=±2%	7a	TO-92L		... 79L06(TO-92)
HA 179L08(P),A(PA)	Hit	Z-IC	-8V, 0.15A, ±4%, A=±2%	7a	TO-92L		... 79L08(TO-92)
HA 179L09(P),A(PA)	Hit	Z-IC	-9V, 0.15A, ±4%, A=±2%	7a	TO-92L		... 79L09(TO-92)
HA 179L10(P),A(PA)	Hit	Z-IC	-10V, 0.15A, ±4%, A=±2%	7a	TO-92L		... 79L10(TO-92)
HA 179L12(P),A(PA)	Hit	Z-IC	-12V, 0.15A, ±4%, A=±2%	7a	TO-92L	79L12/TO-92	7a ... 79L12(TO-92)
HA 179L15(P),A(PA)	Hit	Z-IC	-15V, 0.15A, ±4%, A=±2%	7a	TO-92L		... 79L15(TO-92)
HA 179 L05...L15UA	Hit	Z-IC	=HA 179L05...L15: Min	39a	SOT-89		... 79Lxx (SOT-89)
HA 179 M05 FM,FMP	Hit	Z-IC	Iso, -5V, 0.5A	17c	TO-220 Iso	(7905/TO-220) ³	17c ... 79M05... (TO-220 Iso)
HA 179 M06 FM,FMP	Hit	Z-IC	Iso, -6V, 0.5A	17c	TO-220 Iso		... 79M06... (TO-220 Iso)
HA 179 M06 FM,FMP	Hit	Z-IC	Iso, -12V, 0.5A	17c	TO-220 Iso	(7912/TO-220) ³	17c ... 79M12... (TO-220 Iso)
HA 179 M15 FM,FMP	Hit	Z-IC	Iso, -15V, 0.5A	17c	TO-220 Iso	(7915/TO-220) ³	17c ... 79M15... (TO-220 Iso)
HA 1107	Hit	LIN-IC	VC, Sound IF				-
HA 1108	Hit	LIN-IC	TV, AFT	14-DIP			-
HA 1110	Hit	LIN-IC	Video-Verstärker/Amplifier	TO-101			CA 3001
HA 1115	Hit	LIN-IC	Stereo-Decoder	14-DIP			HA 1120
HA 1120	Hit	LIN-IC	Stereo-Decoder	14-DIP			HA 1115
HA 1124	Hit	LIN-IC	TV, Sound IF	14-DIP			-HA 1125
HA 1125	Hit	LIN-IC	TV, Sound IF	14-DIP			AN 241, CA 3065, KA 2101, LA 1365, LM 3065, MC 1358, TA 7176, ULN 2165
HA 1126	Hit	LIN-IC	TV, AFT	14-DIP			LA 1364, M 5135, TA 7070
HA 1127(P)	Hit	LIN-IC	TV, 5x Trans.-Array, 20/15V, 50mA, 460MHz	14-DIP,DIP			CA 3045
HA 1127 FP	Hit	LIN-IC	=HA 1127(P): SMD	14-MDIP			-
HA 1137(W)	Hit	LIN-IC	FM IF, LF Inp, AFC	16-DIP			-
HA 1138	Hit	LIN-IC	AM Inp,Mx,Os,IF, Demodulator	16-DIP			-
HA 1142	Hit	LIN-IC	Stereo-Decoder	14-DIP			-
HA 1144	Hit	LIN-IC	TV, Video IF	14-DIP			-
HA 1148	Hit	LIN-IC	CTV, VA Korrektur/Correction	14-DIP			-
HA 1149	Hit	LIN-IC	FM Muting	14-DIP			-
HA 1150	Hit	LIN-IC	FM IF	16-DIP			-
HA 1151	Hit	LIN-IC	AM HF, IF	14-DIP			-
HA 1152	Hit	LIN-IC	CTV, Video IF	14-DIP			-
HA 1154	Hit	LIN-IC	VC, Sound IF				-
HA 1156(W)	Hit	LIN-IC	Stereo-Decoder	14-DIP			-
HA 1160	Hit	LIN-IC	TV, HA Sync, HA Os	7-SIP			-
HA 1166(W)	Hit	LIN-IC					-
HA 1167	Hit	LIN-IC					-
HA 1173	Hit	LIN-IC	FM Demodulator	14-DIP			-
HA 1190	Hit	LIN-IC	Sensor f. 4 Tasten/Touch Switches	16-DIP	SAS 560 S	16-DIP	SAS 560S
HA 1194	Hit	LIN-IC	Sensor f. 4 Tasten/Touch Switches	16-DIP	SAS 570 S	16-DIP	SAS 570S
HA 1196	Hit	LIN-IC	Stereo-Decoder	16-DIP			-
HA 1197	Hit	LIN-IC	AM Tuner, IF	16-DIP	HA 1197*	16-DIP	-
HA 1199	Hit	LIN-IC	AM Tuner	16-DIP	HA 1199*	16-DIP	-
HA 1201	Hit	LIN-IC	FM IF	8-DIP			(=HA 1211) ¹⁰
HA 1202	Hit	LIN-IC	FM IF	8-DIP			-
HA 1203	Hit	LIN-IC	FM IF	8-DIP			-
HA 1211	Hit	LIN-IC	FM IF	8-SIP	HA 1211*	8-SIP	(=HA 1201) ¹⁰
HA 1303	Hit	OP-IC		TO-100			-
HA 1306(W)	Hit	LIN-IC	Audio Out, 18V, 2.25A, 3.5W(13V/4Ω)	10-QIP+f			-
HA 1314	Hit	LIN-IC					-
HA 1317(V,W,VU,WU)	Hit	LIN-IC	Audio Out, 36V, 8W(26V/8Ω)	10-DIP+g			-
HA 1319	Hit	LIN-IC	Audio Inp,Out, 12V, 1W(6V/4Ω)	14-DIP			-
HA 1322(W)	Hit	LIN-IC	Audio Out, 18V, 2.25A, 5.5W(13V/4Ω)	10-DIP+f			-
HA 1324	Hit	LIN-IC	Audio Out, 18V, 2.25A, 4.5W(13V/4Ω)	10-DIP+g			-
HA 1325	Hit	LIN-IC	Audio Out, 20V, 1.25A, 2W(13V/8Ω)	12-DIP+a			-
HA 1327	Hit	LIN-IC	4-Kanal-/Channel Decoder	16-DIP			-
HA 1328	Hit	LIN-IC	Matrix f. 4-Kanal-/Channel Decoder	16-DIP			-
HA 1329	Hit	LIN-IC	Audio Out, 9V, 1.4A, 2.5W(6V/8Ω)	12-DIP+a			-
HA 1333	Hit	LIN-IC	CD-4 Demodulator	16-DIP			-
HA 1334	Hit	LIN-IC	CD-4 Demodulator	16-DIP			-
HA 1338	Hit	LIN-IC	Audio Out, 33V, 4.1A, 6W(24V/8Ω)	10-QIP+f			-
HA 1339(A)	Hit	LIN-IC	Audio Out, 18V, 4.5A, 5.5W(13V)	10-SILP+a			-
HA 1339(A)R	Hit	LIN-IC	=HA1339: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a			-
HA 1342(A)	Hit	LIN-IC	Audio Out, 18V, 4.5A, 5.5W(13V)	10-SILP+a			-
HA 1342(A)R	Hit	LIN-IC	=HA1342: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a			-
HA 1345 V	Hit	LIN-IC	Audio Out, 36V, 8W(26V/8Ω)	10-SILP			-
HA 1350	Hit	LIN-IC	Audio Out, ±30V, 7.5A, 18W(±25V/8Ω)	10-SILP			HA 1370
HA 1361	Hit	LIN-IC	Audio Out, 9V, 2.25A, 1W(6V/4Ω)	12-DIP+b			-
HA 1364	Hit	LIN-IC	TV, Sound IF, LF Out, 1.5W(24V/16Ω)	12-QIP+b			-
HA 1366 W	Hit	LIN-IC	Audio Out, 18V, 4.5A, 5.5W(13V/4Ω)	10-SILP+a			-
HA 1366 WR	Hit	LIN-IC	=HA1366W: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a			-
HA 1367(A)	Hit	LIN-IC	Recorder, Audio Inp,Out, 9V, 2.25A, 2.2W(6V/4Ω)	20-DIP+b			-
HA 1368	Hit	LIN-IC	Audio Out, 18V, 4.5A, 5.3W(13V/4Ω)	10-SILP+a	HA 1368*	10-SILP+a	-
HA 1368 R	Hit	LIN-IC	=HA1368: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a			-
HA 1370	Hit	LIN-IC	Audio Out, ±30V, 7.5A, 18W(±25V/4...8Ω)	10-SILP			-
HA 1371	Hit	LIN-IC	Audio Out, 15V, 3A, 7.3W(9V/4Ω)	12-QIP+b			-
HA 1372	Hit	LIN-IC	Audio Out, 18V, 4.5A, 5.5W(13V/4Ω)	10-DIP+f			-
HA 1374	Hit	LIN-IC	Dual Audio Out, 22V, 2.8A, 2x3W(15V/8Ω)	10-SILP+a			-
HA 1374 A	Hit	LIN-IC	=HA 1374: 25V, 3.2A, 2x4W(17V/8Ω)	10-SILP+a			-
HA 1377(A)	Hit	LIN-IC	Dual Audio Out, 18V, 4.5A, 2x5.8W(13V/4Ω)	12-SIL	HA 1377	12-SIL	-
HA 1384(A)	Hit	LIN-IC	Audio Out, 18V, 4A, 20W(13.2V/4Ω, BTL)	12-SIL			-
HA 1385	Hit	LIN-IC	CTV, VA Out, Ucc=110V	17/5Pin	TO-220/5		-

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
HA 1388	Hit	LIN-IC	Audio Out, 18V, 4A, 18W(13,2V/4Ω)	12-SIL	HA 1388	12-SIL	-
HA 1389	Hit	LIN-IC	Audio Out, 30V, 3,73A, 7W(22V/8Ω)	10-SILP+a			-
HA 1389 R	Hit	LIN-IC	=HA1389: spiegelb. Pinbelegung/Reverse Pinning	10-SILP+a			-
HA 1392	Hit	LIN-IC	Dual Audio Out, 20V, 4A, 2x4,3W(12V/4Ω)	12-SIL	HA 1392	12-SIL	-
HA 1393	Hit	LIN-IC	Audio Out, 18V, 4A, 19W(13,2V/4Ω, BTL)	12-SIL			-
HA 1394	Hit	LIN-IC	Dual Audio Out, 35V, 4,5A, 2x8,2W(25V/8Ω)	12-SIL	HA 1394	12-SIL	-
HA 1396	Hit	LIN-IC	Audio Out, 18V, 4A, 20W(13V/4Ω)	12-SIL	HA 1396*	12-SIL	-
HA 1397	Hit	LIN-IC	Audio Out, ±30V, 7,5A, 20W(±22V/8Ω)	12-SIL			-
HA 1398	Hit	LIN-IC	Audio Out	12-SIL	HA 1398	12-SIL	-
HA 1403	Hit	Z-IC	Tuner Stabi, 33V, 10mA	2d	TO-18	TAA 550	2g -TAA 550
HA 1406	Hit	LIN-IC	Audio Inp	8-SIP	HA 1406*	8-SIP	-
HA 1451	Hit	LIN-IC	Dual Audio Inp	14-DIP			-
HA 1452(W)	Hit	LIN-IC	Dual Audio Inp	14-DIP			-
HA 1457(W)	Hit	LIN-IC	Audio Inp In, Ucc=±25V	8-SIP			-
HA 1607	Hit	LIN-IC	Monostab. Multivibrator	8-DIP			-
HA 1806 M	Hit	KOP-IC	Dual, 18V, -30...+80°	TO-100			-
HA 1807	Hit	KOP-IC	Dual, 18V, -30...+80°	14-DIP			-
HA 1807 M	Hit	KOP-IC	=HA 1807: Fig. →	TO-101			-
HA 1812(GS,PS)	Hit	KOP-IC	20V, 200mA, -20...+75°	8-DIC,DIP			-
HA 1813(PS)	Hit	KOP-IC	18V, -20...+75°	8-DIP			-
HA 1835 P	Hit	Z-IC	5V, Watch Dog Timer, Reset	14-DIP			-
HA 1848 P	Hit	Z-IC	5V, Watch Dog Timer, Reset	14-DIP			-
HA 1902	Hit	LIN-IC	Dual Sensor-Verstärker/Amplifier	16-DIP			-
HA 11107	Hit	IC					-
HA 11120	Hit	LIN-IC	AM Tuner, AM/FM IF	16/20-DIP			-
HA 11122	Hit	LIN-IC	Recorder, 2x Rec/Play Amp.	16-DIP			-
HA 11123(W)	Hit	LIN-IC	AM/FM IF, AFC, AGC	16/20-DIP			-
HA 11211	Hit	LIN-IC	AM Tuner, AM/FM IF	16/20-DIP			-
HA 11215(A)	Hit	LIN-IC	CTV, IF, Video Signal, AGC	24-DIP	HA 11215(A)*	24-DIP	-
HA 11218	Hit	LIN-IC	TV, HA/VA Sync., Os	16/20-DIP			-
HA 11219	Hit	LIN-IC	FM Noise Suppression	16-DIP			-
HA 11220	Hit	LIN-IC	CTV, Video IF	22-DIP			-
HA 11221	Hit	LIN-IC	TV, Video IF	16-DIP			-
HA 11222	Hit	LIN-IC	CTV, NTSC Chroma Signal	28-DIP			-
HA 11223(W)	Hit	LIN-IC	Stereo-Decoder	16-DIP			-
HA 11225	Hit	LIN-IC	FM IF	16-DIP	HA 11225	16-DIP	-
HA 11226	Hit	LIN-IC	Dual Dolby B System	16/20-DIP			-
HA 11226 MP	Hit	LIN-IC	=HA 11226: SMD	18-FLP			-
HA 11227	Hit	LIN-IC	Stereo-Decoder	16-DIP	BA 1330	16-DIP	AN7410, BA1330, KA2261, LA3361, TA7604
HA 11229	Hit	LIN-IC	TV, Sound IF	14-DIP	HA 11229*	14-DIP	-
HA 11235	Hit	LIN-IC	CTV, HA/VA Sync., Os, 60/15734Hz	16/20-DIP			-
HA 11236		LIN-IC					-
HA 11238	Hit	LIN-IC	CTV, Video IF	22-DIP			-
HA 11244	Hit	LIN-IC	TV, Sync. Signal	16-DIP	HA 11244*	16-DIP	-
HA 11247	Hit	LIN-IC	CTV, NTSC Chroma Signal	16/20-DIP			-
HA 11247 MP	Hit	LIN-IC	=HA 11247: SMD	18-MP			-
HA 11251	Hit	LIN-IC	AM/FM IF, Demodulator	16-DIP			-
HA 11401	Hit	LIN-IC	TV, Video Signal	16-DIP	HA 11401*	16-DIP	-
HA 11405	Hit	LIN-IC	CTV, Video IF	16-DIP			-
HA 11408 A	Hit	LIN-IC	TV, Video Signal	28-DIP			-
HA 11409	Hit	LIN-IC	CTV, NTSC VIR	16-DIP			-
HA 11410	Hit	LIN-IC	TV	28-DIP			-
HA 11412 A	Hit	LIN-IC	CTV, NTSC Chroma Signal	28-DIP			-
HA 11414	Hit	LIN-IC	TV, Sync. Signal	16-DIP			-
HA 11417	Hit	LIN-IC	CTV, NTSC Chroma Signal, Demodulator	24-DIP			-
HA 11423	Hit	LIN-IC	TV, Sync., VA Os, Blanking	16/20-DIP	HA 11423	16/20-DIP	-
HA 11423 MP	Hit	LIN-IC	=HA 11423: SMD	18-MP			-
HA 11431	Hit	LIN-IC	CTV, Einstellkombi/DC Control (NTSC)	28-DIP			-
HA 11431 NT	Hit	LIN-IC	=HA 11431: Fig. →	30-SDIP			-
HA 11433	Hit	LIN-IC	TV Stereo Sound System	16-DIP			-
HA 11436 A	Hit	LIN-IC	CTV, Chroma System (NTSC)	28-DIP			-
HA 11440(A)	Hit	LIN-IC	CTV, Video IF System, lagc<0,5mA	16-DIP			-
HA 11441	Hit	LIN-IC	TV, HA/VA Os, Sync., Blanking	16/20-DIP			-
HA 11441 MP	Hit	LIN-IC	=HA 11441: SMD	18-MP			-
HA 11442	Hit	LIN-IC	=HA11440(A): lagc<1,5mA	16-DIP			-
HA 11443	Hit	LIN-IC	TV, Video/Sound IF	28-DIP			-
HA 11445	Hit	LIN-IC	TV, Video/Sound IF	28-DIP			-
HA 11465 A	Hit	LIN-IC	CTV, Video System, Sync. Signal	16/20-DIP			-
HA 11466 S	Hit	LIN-IC	HF-Modulator f. VC, µComp, Ucc=5V	16-DIP			-
HA 11476 NT	Hit	LIN-IC	TV/VC, Video/Sound IF, Video Signal	30-SDIP			-
HA 11477 NT	Hit	LIN-IC	Video-/Audio-Umschalter/Switch	30-SDIP			-
HA 11485 BNT	Hit	LIN-IC	TV/VC, Video/Sound IF, FM Demodulator	30-SDIP			-
HA 11498	Hit	LIN-IC	Digital Video Processor	42-DIP			-
HA 11505	Hit	LIN-IC	Video-Verst./Amplifier, 100MHz, Ucc=5V	24-SDIP+b			-
HA 11508	Hit	LIN-IC	CTV, Video-/Audio-Umschalter/Switch, Ucc=8...13,2V	20-DIP			-
HA 11510 NT	Hit	LIN-IC	CTV,VC, FB Interface	30-SDIP			-
HA 11511 CNT	Hit	LIN-IC	CTV, Video-/Chroma Processor (NTSC)	42-SDIP			-
HA 11513	Hit	LIN-IC	5-Kanal/Channel Video-Umschalter/Switch, Ucc=12V	16-DIP			-
HA 11517 BNT	Hit	LIN-IC	TV, HA/VA Os, Sync., Blanking	30-SDIP			-
HA 11525 MP	Hit	LIN-IC	VC, Digital Signal Processor (NTSC)	28-MP			-
HA 11530 MP	Hit	LIN-IC	VC, Digital Signal Processor (NTSC)	28-MP			-
HA 11531 NT	Hit	LIN-IC	VC, Video-/Chroma Processor (NTSC)	42-SDIP			-
HA 11532 MP	Hit	LIN-IC	VC, Digital Chroma Processor (NTSC)	28-MP			-
HA 11533 NT	Hit	LIN-IC	RGB Video-Verst./Amplifier	24-SDIP+b			-
HA 11535 MP	Hit	LIN-IC	VC, HA/VA-Sync., Killer Detector (PAL)	28-MP			-
HA 11536 MP	Hit	LIN-IC	=HA 11535: R-Y, B-Y Signal (PAL)	28-MP			-
HA 11539 NT	Hit	LIN-IC	CTV,VC, Tuning-System Interface	22-SDIP			-
HA 11544	Hit	LIN-IC	Multiplex Video Switch	16-DIP			-
HA 11545 A	Hit	LIN-IC	FM, Video HF Modulator, Ucc=5V	16-DIP			-
HA 11556 NT	Hit	LIN-IC	CTV/VC, Video IF System	22-SDIP			-
HA 11559 NT	Hit	LIN-IC	CTV, Verzögerungsleitung/Delay Line	30-SDIP			-
HA 11560 FP	Hit	LIN-IC	SMD, VC, HF Modulator, Ucc=5V	16-MDIP			-
HA 11561	Hit	LIN-IC	CTV, Color Signal Matrix	16-DIP			-

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
HA 11566 NT	Hit	LIN-IC	CTV,VC, Split Video & Sound IF f. SAW Filter	22-DIP			-
HA 11569 FS	Hit	LIN-IC	CTV,VC, PIP Processor (NTSC)	80-MP			-
HA 11571 AF,BF	Hit	LIN-IC	CTV,VC, BS Tuner PLL, AGC, AFC, IF, Video	28-MP/4TAB			-
HA 11575 F	Hit	LIN-IC	CTV,VC, BS Tuner PLL, AGC, AFC, IF, Video	28-MP/4TAB			-
HA 11579	Hit	LIN-IC	CTV,VC, PIP Processor (NTSC)	56-MP			-
HA 11580	Hit	LIN-IC	CTV, Chroma Signal	24-DIP			-
HA 11701	Hit	LIN-IC	VC, FM Signal	16/20-DIP			-
HA 11702	Hit	LIN-IC	VC, Kopfvorverst./Head Preamp.	16/20-DIP	HA 11702*	16/20-DIP	-
HA 11703	Hit	LIN-IC	VC, FM Signal	20-DIP			-
HA 11704	Hit	LIN-IC	VC, Color Signal	16/20-DIP			-
HA 11705	Hit	LIN-IC	VC, Color AFC	16/20-DIP			-
HA 11706	Hit	LIN-IC	VC, Color APC	16/20-DIP	HA 11706*	16/20-DIP	-
HA 11707	Hit	LIN-IC	VC, Servo	28-DIP			-
HA 11710	Hit	LIN-IC	VC, Chroma	16/20-DIP	HA 11710*	16/20-DIP	-
HA 11711	Hit	LIN-IC	VC, Servo	28-DIP			-
HA 11712 A	Hit	LIN-IC	VC, NTSC, VIR	16-DIP			-
HA 11713	Hit	LIN-IC	VC, Servo	16-DIP			-
HA 11714	Hit	LIN-IC	VC, Servo	16/20-DIP			-
HA 11715	Hit	LIN-IC	VC, Servo	12-QIP+a			-
HA 11716	Hit	LIN-IC	VC, Luminance Signal	20-DIP	HA 11716*	20-DIP	-
HA 11717	Hit	LIN-IC	VC, Color AFC	16/20-DIP	HA 11717*	16/20-DIP	-
HA 11718	Hit	LIN-IC	VC, Luminance Signal	16-DIP	HA 11718*	16-DIP	-
HA 11719	Hit	LIN-IC	Video Camera Signal	16/20-DIP			-
HA 11720	Hit	LIN-IC	Video Camera Signal	16/20-DIP			-
HA 11722	Hit	LIN-IC	VC, Servo	14-DIP			-
HA 11724	Hit	LIN-IC	VC, Rec/Play Amp.	28-DIP			KA 2984
HA 11725	Hit	LIN-IC	VC, Video Signal	28-DIP			KA 2985
HA 11726	Hit	LIN-IC	VC, Chroma Signal	28-DIP			KA 2986
HA 11727	Hit	LIN-IC	VC, Chroma Signal	28-DIP			KA 2987
HA 11732	Hit	LIN-IC	Video Camera Signal	16-DIP			-
HA 11738	Hit	LIN-IC					-
HA 11741	Hit	LIN-IC	VC, Servo Controller	28-DIP			KA 2988, µPC 1536C
HA 11744	Hit	LIN-IC	VC, Video Rec/Play Amp.	28-DIP			KA 2944, µPC 1534C
HA 11744 NT	Hit	LIN-IC	=HA 11744: Fig. >	30-SDIP			-
HA 11745	Hit	LIN-IC	VC, Video Signal System	28-DIP			KA 2945, µPC 1524A
HA 11745 NT	Hit	LIN-IC	=HA 11745: Fig. >	30-SDIP			-
HA 11752	Hit	LIN-IC	=HA 11772: FM AGC	16-DIP			-
HA 11770 AMP	Hit	LIN-IC	Camera, PAL/SECAM Signal Processor	44-MP			-
HA 11772	Hit	LIN-IC	VC, 2-Kanal/Channel Vorverst./Pre-Amp.	16-DIP			HA 11752
HA 11776 AMP	Hit	LIN-IC	Camera, Encoder	28-MP			-
HA 11787	Hit	LIN-IC	VC, Drop Out Compensator	16-DIP			-
HA 11844 BMP	Hit	LIN-IC	Camera, Weiss/White-Balance	28-MP			-
HA 11856 ANT	Hit	LIN-IC	VC, Color Signal Processor (NTSC)	42-SDIP			-
HA 11864 MP	Hit	LIN-IC	VC, VHS-C, FM Signal Processor	44-MP			-
HA 11870 ANT	Hit	LIN-IC	VC, 4-Kanal/Channel Vorverst./Pre-Amp.	30-SDIP			-
HA 11876 MP	Hit	LIN-IC	=HA 11876NT: SMD	44-MP			-
HA 11876 NT	Hit	LIN-IC	VC, VHS-C, 4-Kanal/Channel Vorverst./Pre-Amp.	42-SDIP			-
HA 11882 AMP	Hit	LIN-IC	Camera, 4-Kanal/Channel Processor	44-MP			-
HA 11883 MP	Hit	LIN-IC	Camera, NTSC/PAL Chroma Encoder	18-MP			-
HA 12001 W	Hit	LIN-IC	Recorder, Funktionsstrg./Mechanic Control	22-DIP			-
HA 12002(W)	Hit	LIN-IC	Lautspr.-Schutz/Speaker Protection, Ucc=45V	8-SIP			-
HA 12003	Hit	IC					-
HA 12005	Hit	LIN-IC	LF Inp In, Dolby	16-DIP			-
HA 12006	Hit	LIN-IC	Recorder Rec/Play Amp.	16/20-DIP			-
HA 12009	Hit	LIN-IC	7-Segment Decoder f. Digital Tuning	42-DIP			-
HA 12010	Hit	LIN-IC	FLT-Treiber/Driver	16-DIP			-
HA 12016	Hit	LIN-IC	PLL FM MPX Stereo-Decoder, Ucc=13V	16-DIP			-
HA 12017	Hit	LIN-IC	Audio Vorverst./Preamp., In, Ucc=±24V	8-SIP	(no Pin2)		-
HA 12018	Hit	LIN-IC	Stereo-Decoder	16-SQP			-
HA 12019	Hit	LIN-IC	Recorder, Pegelanzeige/Level Meter, log.	16-DIP			-
HA 12020	Hit	LIN-IC	Recorder, Equalizer	28-DIP			-
HA 12022	Hit	LIN-IC		16/20-DIP			-
HA 12024	Hit	LIN-IC	Recorder	16/20-DIP			-
HA 12026	Hit	LIN-IC	Stereo-Decoder	16-DIP			-
HA 12027	Hit	LIN-IC	Recorder, Dolby B System	16/20-DIP			-
HA 12028	Hit	LIN-IC	Recorder, Verstärker/Amplifier	22-DIP			-
HA 12029	Hit	LIN-IC	8-Bit µComp Interface	18-FLP			-
HA 12030	Hit	LIN-IC	8-Bit µComp Interface	16-DIP			-
HA 12031	Hit	LIN-IC	Stereo-Decoder	28-DIP			-
HA 12032	Hit	LIN-IC	Anzeigetreiber/Meter Driver	18-DIP			-
HA 12075 MP	Hit	LIN-IC	8mm-VC, FM Processor	44-MP			-
HA 12093 MP	Hit	LIN-IC	=HA 12093NT: SMD	44-MP			-
HA 12093 NT	Hit	LIN-IC	VC, VHS HiFi FM Signal	42-SDIP			-
HA 12095 NT	Hit	LIN-IC	CD, Vorverst./Preamp., Servo Amp., Ucc=±5V	42-SDIP			-
HA 12096 NT	Hit	D/A-IC	16 Bit, Digital Audio, Ucc=±5V	22-SDIP			-
HA 12108 MP	Hit	D/A-IC	=HA 12108NT: SMD	44-MP			-
HA 12108 NT	Hit	D/A-IC	CD/DAT, 16 Bit, Stereo, Digital Audio, S/H, Ucc=5V	22-SDIP			-
HA 12127 ANT	Hit	LIN-IC	Stereo FM Demodulation, CX NR System, Ucc=±5V	56-SDIP			-
HA 12132 MP	Hit	A/D-D/A-IC	SMD, Dual, 16 Bit, Dig. Audio (R-DAT), Sample/Hold	44-MP			-
HA 12133 MP	Hit	LIN-IC	SMD, R-DAT, Dual, Rec/Play Amp, Equal., Ucc=5V	44-MP			-
HA 12134 A	Hit	LIN-IC	Dual Dolby-B NR System, Ucc=6.5...16V, Level=300mV	16-DIP			-
HA 12135 A	Hit	LIN-IC	Dual Dolby-B NR System, Ucc=8...16V, Level=450mV	16-DIP			-
HA 12136 A	Hit	LIN-IC	Dual Dolby-B NR System, Ucc=9.5...16V, Level=580mV	16-DIP			-
HA 12136 AF	Hit	LIN-IC	=HA 12134...12136: SMD	16-MDIP			-
HA 12141 NT	Hit	LIN-IC	Dual Dolby-B/C NR System, Ucc=7.5...16V	30-SDIP			-
HA 12142 NT	Hit	LIN-IC	Dual Dolby-B/C NR System, Ucc=9.5...16V	30-SDIP			-
HA 12144 FP	Hit	LIN-IC	SMD FM Front End, AGC, f. Auto-/Car Radio, Ucc=12V	16-MDIP			-
HA 12151 MA	Hit	LIN-IC	SMD, Dual Dolby-B/C NR System, Ucc=7.5...16V	44-MP			-
HA 12153 MA	Hit	LIN-IC	SMD, Dual Dolby-B/C NR System, Ucc=9.5...16V	44-MP			-
HA 12154 MA	Hit	LIN-IC	DAT Recorder, Rec/Play Amp, Equalizer, Ucc=5V	56-MP			-
HA 12155 NT	Hit	LIN-IC	Recorder, Dual Audio Signal Processor, Dolby-B/C	64-SDIP			-
HA 12156 MA	Hit	LIN-IC	CD, Vorverst./Preamp., Tracking f. Portable	44-MP			-
HA 12157 NT	Hit	LIN-IC	Recorder, Audio Signal Processor, Dolby-B/C	64-SDIP			-

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
HA 12158	Hit	LIN-IC	=HA 12158NT: SMD	56-MP			-
HA 12158 NT	Hit	LIN-IC	CD, Servo System, Ucc=5V	56-SDIP			-
HA 12160	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=8,2...16V	56-MP			-
HA 12161 FP	Hit	LIN-IC	SMD, Dual Dolby-B/C NR System, Ucc=7,5...16V	28-MDIP			-
HA 12162 FP	Hit	LIN-IC	SMD, Dual Dolby-B/C NR System, Ucc=9,5...16V	28-MDIP			-
HA 12163	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=6,5...16V	56-MP			-
HA 12164	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=7,2...16V	56-MP			-
HA 12165	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=8,5...16V	56-MP			-
HA 12166 F	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=6,5...16V	48-MP			-
HA 12167 FB	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B/C, Ucc=12...15V	80-MP			-
HA 12168 NT	Hit	LIN-IC	SMD, CD, Servo System, Ucc=5V, =HA 12158(Pin9)	56-MP			-
HA 12169 FB	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B/C, Ucc=11...15V	80-MP			-
HA 12170 NT	Hit	LIN-IC	Dual Dolby-B/C NR System, Ucc=12...16V	30-SDIP			-
HA 12171 NT	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=9,5...16V	56-SDIP			-
HA 12172 NT	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=9,5...16V	56-SDIP			-
HA 12173	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B/C, Ucc=7...16V	56-MP			-
HA 12174	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B/C, Ucc=8...16V	56-MP			-
HA 12175	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B/C, Ucc=9,5...16V	56-MP			-
HA 12177	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B/C, Ucc=12...16V	56-MP			-
HA 12178 F	Hit	LIN-IC	CD, Servo System, Ucc=5V	56-MP			-
HA 12179 F	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=6,8...16V	56-MP			-
HA 12180 F	Hit	LIN-IC	FM IF (H.U.C. GmbH DYNAS System), Mute, Ucc<16V	56-MP			-
HA 12181 FP	Hit	LIN-IC	SMD, AM Störunterdr./Noise Reduction, Ucc7...10V	16-MDIP			-
HA 12182 F	Hit	LIN-IC	=HA 12182NT: SMD	56-MP			-
HA 12182 NT	Hit	LIN-IC	Recorder, Audio Processor, Dolby-B, Ucc=12...16V	56-SDIP			-
HA 12402	Hit	LIN-IC	AM Inp, AM/FM IF, Audio Out, 0,45W(6V/8Ω)	16-DIP	TDA 1083	16-DIP	A 283D, KA 22424, TA 7613AP, TDA 1083, ULN 2204
HA 12404	Hit	LIN-IC	AM/FM Frequ.-Zähler/Counter, 7-Segment Decoder	22-DIP			-
HA 12405	Hit	LIN-IC	AM/FM Frequ.-Zähler/Counter, 7-Segment Decoder	22-DIP			-
HA 12411	Hit	LIN-IC	FM IF, AGC, AFC	16-DIP			-
HA 12412	Hit	LIN-IC	FM IF, Dem, Mute, AFC, Ucc=13V	16-DIP			-
HA 12413	Hit	LIN-IC	AM/FM IF, Dem, Signal Meter, Ucc=3...14V	16-DIP			BA 4220, KA 2243
HA 12417	Hit	LIN-IC	AM Tuner, IF	16-SQP			-
HA 12418	Hit	LIN-IC	FM IF	16-SQP			-
HA 12419	Hit	LIN-IC	FM Impulszähler/Pulse Count	16-DIP			-
HA 12427	Hit	LIN-IC	AM Tuner, IF	16-DIP			-
HA 12428	Hit	LIN-IC	AM Tuner, IF, AGC, Ucc=7,5...16V	16+4-DIP			-
HA 12428 V	Hit	LIN-IC	=HA 12428: Fig. →	21-SQP			-
HA 12430	Hit	LIN-IC	AM Tuner, AM/FM IF, AGC, Signal Meter, Ucc=3...12V	20-DIP			-
HA 12438 CFP	Hit	LIN-IC	SMD, FM Tuner, FM IF, AGC, f. Car R., Ucc=6,5...10V	16-MDIP			-
HA 13001	Hit	LIN-IC	Dual LF Out, 18V, 4,5A, 2x5,5W(13V/4Ω), 17,5W(BTL)	12-SIL	HA 13001	12-SIL	-
HA 13002	Hit	LIN-IC	Schaltregler/Switching Regulator	16-DIP			-
HA 13006	Hit	LIN-IC	Video Disk, Motorregler/Motor Control	20-DIP+b			-
HA 13007	Hit	LIN-IC	Quad Relais, Solenoid, Motor Drv, Ucc=5V, 0,7A	16-DIP			-
HA 13108	Hit	LIN-IC	Dual Audio Out, 18V, 4A, 2x5,5W(13,2V/4Ω)	12-SIL			-
HA 13116	Hit	LIN-IC	Audio Out, 18V, 4A, 20W(13,2V/4Ω, BTL)	15-SQL			-
HA 13117	Hit	LIN-IC	Audio Out, 18V, 4A, 14W(13,2V/4Ω, BTL)	15-SQL			-
HA 13118	Hit	LIN-IC	Audio Out, 26V, 4A, 18W(13,2V/4Ω, BTL)	15-SQL	HA 13118	15-SQL	-
HA 13119	Hit	LIN-IC	Dual, Audio Out, 18V, 4A, 2x5,5W(13,2V/4Ω)	15-SQL	HA 13119	15-SQL	-
HA 13127	Hit	LIN-IC	Dual BTL LF Out, 18V, 4A, 2x17W(14,4V/4Ω), Gv=50dB	16-SQL			HA 13128
HA 13128	Hit	LIN-IC	Dual BTL LF Out, 18V, 4A, 2x22W(14,4V/4Ω), Gv=50dB	16-SQL			-
HA 13130	Hit	LIN-IC	=HA 13127: Voltage Gain=40dB	16-SQL			HA 13135
HA 13135	Hit	LIN-IC	=HA 13128: Voltage Gain=40dB	16-SQL			-
HA 13143	Hit	LIN-IC	CD, 4x BTL Treiber/Driver f. Servo, Ucc=7...10V	26-SMDIP+b			-
HA 13150 A	Hit	LIN-IC	Quad BTL Audio Out, 18V, 4A, 4x18W(13,2V/4Ω)	23-SQL			-
HA 13151	Hit	LIN-IC	Quad BTL Audio Out, 18V, 3A, 4x14W(13,2V/4Ω)	23-SQL			-
HA 13152	Hit	LIN-IC	Quad BTL Audio Out, 18V, 3A, 4x14W(13,2V/4Ω)	23-SQL			HA 13151
HA 13403(V)	Hit	LIN-IC	VC, 3-Phase Brushless Motor Drv, Ucc=4,5...13V, 1,5A	23-SQL			-
HA 13403 MP	Hit	LIN-IC	=HA 13403: SMD, Ucc=4,5...5,5V, 1A	28-MP			-
HA 13406 W	Hit	LIN-IC	5,25" HDD, 3-Ph. Brushless Motor Drv	23-SQL			-
HA 13408	Hit	LIN-IC	9-Channel Power Driver, Ucc=5V, 1,5A	23-SQL			-
HA 13412	Hit	LIN-IC	3-Phase Brushless Motor Drv, Ucc=6...15/5...30V, 1A	23-SQL			-
HA 13415	Hit	LIN-IC	4x Solenoid Driver, Ucc=5V, 0,6A	16-DIP			-
HA 13421 A	Hit	LIN-IC	3...5,25" FDD, 2-Phase Stepping Motor Drv, 0,33A	16-DIP			-
HA 13421 AMP	Hit	LIN-IC	=HA 13421A: SMD	18-MP			-
HA 13426	Hit	LIN-IC	5,25" HDD, Spindle Motor Drv, Ucc=12V, 3A	23-SQL			-
HA 13431	Hit	LIN-IC	5,25" FDD, Spindle Motor Drv, Ucc=12V, 1A	23-SQL			-
HA 13432	Hit	LIN-IC	3...3,5" FDD, Spindle Motor Drv, Ucc=12V, 0,5A	24-SDIP+b			-
HA 13432 MP	Hit	LIN-IC	=HA 13432: SMD	28-MP			-
HA 13439 AMP	Hit	LIN-IC	SMD, 2-Ph. Brushl. DC Fan Motor Drv, 7,5...30V, 1,5A	18-MP			-
HA 13440 MP	Hit	LIN-IC	SMD, FDD, 3-Ph. Brushless DC Motor Drv, 12V, 0,7A	28-MP			-
HA 13441(V)	Hit	LIN-IC	HDD, 3-Ph. Brushless DC Motor Drv, 12V, 2A	23-SQL			-
HA 13442(V)	Hit	LIN-IC	=HA 13441(V): 4A	23-SQL			-
HA 13444	Hit	LIN-IC	4x Solenoid Driver, Ucc=5V, 0,6A	16-DIP			-
HA 13447	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=12V, 2,8A	23-SQL			-
HA 13449 MP	Hit	LIN-IC	S-Reg., 4 Outputs, 200kHz, Ucc=12V, Uref=5V	28-MP			-
HA 13455	Hit	LIN-IC	VC, 3-Phase Brushless Motor Drv(1A), S-Reg(1,8A)	24-SDIP+b			-
HA 13456 A	Hit	LIN-IC	FDD, 3-Phase Brushless DC Motor Drv, Ucc=12V, 0,7A	24-SDIP+b			-
HA 13456 AMP	Hit	LIN-IC	=HA 13456A: SMD	28-MP			-
HA 13457 NT	Hit	LIN-IC	VC, 3-Phase Motor Drv, 1A	24-SDIP+b			-
HA 13460 FP	Hit	LIN-IC	SMD, Brushless DC Fan Motor Drv, 7,5...28V, 2x 1,5A	16-MDIP			-
HA 13464 MP	Hit	LIN-IC	SMD, 3-Phase Brushless DC Motor Drv, 0,4A	28-MP			-
HA 13467 NT	Hit	LIN-IC	VC, 3-Phase Brushless Motor Drv, 1A	24-SDIP+b			-
HA 13468 MP	Hit	LIN-IC	SMD, 3-Ph. Brushl. DC Motor Drv, 0,7A, Speed Diskr.	28-MP			-
HA 13470	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=12V, 1,67A	15-SQL			-
HA 13471(A)	Hit	LIN-IC	HDD, 3-Ph. Brushless Motor Drv, 12V, 2A	23-SQL			-
HA 13472(A)	Hit	LIN-IC	=HA 13471(A): 4A	23-SQL			-
HA 13473 MP	Hit	LIN-IC	=HA 13473NT: SMD	28-MP			-
HA 13473 NT	Hit	LIN-IC	FDD, 3-Phase Brushless Motor Drv, Ucc=12V, 0,7A	24-SDIP+b			-
HA 13475 FP	Hit	LIN-IC	=HA 13475MP: Fig. →	16-MDIP			-
HA 13475 MP	Hit	LIN-IC	SMD, 2-Phase Stepping Motor Drv, 12V, 0,33A	18-MP			-
HA 13476 S	Hit	LIN-IC	SMD, 3-Ph. HDD, Brushl. Motor Drv, 1A, Speed Diskr.	26-MDIP+b			-
HA 13480 AS-02	Hit	LIN-IC	SMD, 3-Ph. Motor Drv, 24V, 0,7A, Speed Diskr.	26-MDIP+b			-

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
HA 13480 S	Hit	LIN-IC	SMD, 3-Ph. Motor Drv, 24V, 0,7A, Speed Diskr.	26-MDIP+b		-	-
HA 13481 AFP	Hit	LIN-IC	SMD, HDD, 3-Ph. DC Motor Drv, 12V, 2A, Speed Diskr	26-MDIP+b		-	-
HA 13481 S	Hit	LIN-IC	SMD, HDD, 3-Ph. DC Motor Drv, 12V, 2A, Speed Diskr	26-MDIP+b		-	-
HA 13482	Hit	LIN-IC	HDD, 3-Ph. Brushl.Motor Drv, 12V, 4A, Speed Diskr.	23-SQL		-	-
HA 13483 ANT	Hit	LIN-IC	=HA 13483NT: 0,8A	24-SDIP+b		-	-
HA 13483 (A)MP	Hit	LIN-IC	=HA 13483NT: SMD	28-MP		-	-
HA 13483 NT	Hit	LIN-IC	FDD, 3-Phase Brushless Motor Drv, Ucc=12V, 0,7A	24-SDIP+b		-	-
HA 13488	Hit	LIN-IC	HDD, 3-Ph. Brushl.Motor Drv, 12V, 4A, Speed Diskr.	23-SQL		-	-
HA 13490	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=12V, 0,8A	16-DIP		-	-
HA 13490 FP	Hit	LIN-IC	=HA 13490: SMD	16-MDIP		-	-
HA 13490 MP	Hit	LIN-IC	=HA 13490: SMD	18-MP		-	-
HA 13491 S	Hit	LIN-IC	SMD, HDD, 3-Phase DC Motor Drv, 5V, 12V, 1A	26-MDIP+b		-	-
HA 13492	Hit	LIN-IC	Quad Solenoid Driver, Ucc=7...25V, 0,8A	15-SIL		-	-
HA 13493 MP	Hit	LIN-IC	SMD,FDD, 3-Phase Brushless Motor Drv, Ucc=5V, 0,7A	28-MP		-	-
HA 13499 AMP,MP	Hit	LIN-IC	SMD,FDD, 3-Phase Brushless Motor Drv, Ucc=5V, 0,7A	28-MP		-	-
HA 13501 F	Hit	LIN-IC	=HA 13501S: Fig. ->	56-MP		-	-
HA 13501 S	Hit	LIN-IC	HDD, 3-Phase Brushless Motor Drv, Ucc=5V, 1,2A	26-MDIP+b		-	-
HA 13509 F	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=5V, 0,4A	28-MP/4TAB		-	-
HA 13511 F	Hit	LIN-IC	FDD, 3-Phase Brushless Motor Drv, Ucc=5V, 0,7A	28-MP/4TAB		-	-
HA 13513 FNF	Hit	LIN-IC	FDD, 3-Phase Brushless Motor Drv, Ucc=5V, 0,7A	28-MP/4TAB		-	-
HA 13518 FP	Hit	LIN-IC	HDD, 3-Phase Brushless Motor Drv, Ucc=5V, 1,2A	26-MDIP+b		-	-
HA 13520 F	Hit	LIN-IC	HDD, Spindel(1A) & Voice Coil(0,4A) Motor Drv, 5V	28-MP/4TAB		-	-
HA 13524(S)	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=12V, 2,8A	23-SQL/SIL		-	-
HA 13524 FP	Hit	LIN-IC	=HA 13524(S): SMD	26-MDIP+b		-	-
HA 13525 FP	Hit	LIN-IC	HDD, Spindel(1,5A) & Voice Coil(1A) Motor Drv, 12V	26-MDIP+b		-	-
HA 13529 FP	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=12V, 0,8A	26-MDIP+b		-	-
HA 13532 NT	Hit	LIN-IC	3-Phase Stepping Motor Drv, Ucc=24V	24-SDIP		-	-
HA 13534 FP	Hit	LIN-IC	3-Ph. Brushless Motor Drv, Ucc=24V, 0,7A, >3500rpm	26-MDIP+b		-	-
HA 13535 FP	Hit	LIN-IC	=HA 13534FP: 7000...18000rpm	26-MDIP+b		-	-
HA 13536 F	Hit	LIN-IC	FDD, 3-Phase Brushless Motor Drv, Ucc=5V, 0,7A	28-MP/4TAB		-	-
HA 13537 F	Hit	LIN-IC	FDD, 3-Phase Brushless Motor Drv, Ucc=12V, 0,8A	28-MP/4TAB		-	-
HA 13537 NT	Hit	LIN-IC	=HA 13537F: Fig. ->	24-SDIP+b		-	-
HA 13539 FP	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=12V, 1A	26-MDIP+b		-	-
HA 13540 F	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=12V, 1,5A	80-MP		-	-
HA 13542 FP	Hit	LIN-IC	HDD, 3-Phase Brushless Motor Drv, Ucc=12V, 2A	26-MDIP+b		-	-
HA 13544 F	Hit	LIN-IC	HDD, Spindel(1A) & Voice Coil(0,4A) Motor Drv, 5V	28-MP/4TAB		-	-
HA 13549 FP	Hit	LIN-IC	HDD, Voice Coil Motor Drv, Ucc=12V, 1A	26-MDIP+b		-	-
HA 13605	Hit	LIN-IC	3-Phase Brushless Motor Drv, Ucc=20...35V, 1,5A	23-SQP		-	-
HA 13606(S)	Hit	LIN-IC	HDD, 3-Phase Brushless Motor Drv, Ucc=12V, 4,5A	23-SQP/SIL		-	-
HA 13705	Hit	LIN-IC	Hi-Side Solenoid Driver, Udd=7...25V	17/5Pin	TO-220/5	-	-
HA 16103 FPJ	Hit	Z-IC	=HA 16103PJ: SMD	20-MDIP		-	-
HA 16103 PJ	Hit	Z-IC	5V, Watch Dog Timer, Reset	18-DIP		-	-
HA 16107 FP	Hit	LIN-IC	=HA 16107P: SMD	16-MDIP		-	-
HA 16107 P	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, ...600kHz	16-DIP		-	-
HA 16108 FP	Hit	LIN-IC	=HA 16108P: SMD	16-MDIP		-	-
HA 16108 P	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, ...600kHz	16-DIP		-	-
HA 16109 FP	Hit	LIN-IC	=HA 16109P: SMD	16-MDIP		-	-
HA 16109 P	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, ...600kHz	16-DIP		-	-
HA 16111 FP	Hit	LIN-IC	=HA 16111P: SMD	16-MDIP		-	-
HA 16111 P	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, ...600kHz	16-DIP		-	-
HA 16112 F	Hit	CMOS-IC	Spg.-Teiler/Volt. Divider, 10V -1,25+2,5+7,5+8,75V	8-MDIP		-	-
HA 16113 FPJ	Hit	Z-IC	SMD, Dual, 5V, Watch Dog Timer, Reset	24-MDIP		-	-
HA 16114 FP	Hit	LIN-IC	=HA 16114P: SMD	16-MDIP		-	-
HA 16114 P	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, ...600kHz	16-DIP		-	-
HA 16115 F	Hit	CMOS-IC	Spg.-Teiler/Volt. Divider, 10V -1,25+2,5+7,5+8,75V	8-MDIP		-	-
HA 16116 FP	Hit	LIN-IC	SMD, Dual, PWM Schaltreg./Switch. Reg., ...600kHz	20-MDIP		-	-
HA 16117 FA(J)	Hit	CMOS-IC	SMD, Watch Dog Timer, Reset, Threshold Volt.=4,4V	8-MDIP		-	-
HA 16117 FB(J)	Hit	CMOS-IC	=HA 16117FA: Threshold Volt.=4,2V	8-MDIP		-	-
HA 16117 FC(J)	Hit	CMOS-IC	=HA 16117FA: Threshold Volt.=4,0V	8-MDIP		-	-
HA 16118 FP	Hit	CMOS-OP-IC	SMD, Dual, 15V, Iout=±5mA, 0,82V/µs, -20...+75°	8-MDIP		-	-
HA 16118 FPJ	Hit	CMOS-OP-IC	=HA 16118FP: -40...+85°	8-MDIP		-	-
HA 16119 FP	Hit	CMOS-OP-IC	SMD, Dual, 15V, Iout=±5mA, 0,08V/µs, -20...+75°	8-MDIP		-	-
HA 16120 FP	Hit	LIN-IC	SMD,PWM Schaltregler/Switching Regulator, ...600kHz	16-MDIP		-	-
HA 16121 FP	Hit	LIN-IC	SMD, Dual, PWM Schaltreg./Switch. Reg., ...600kHz	20-MDIP		-	-
HA 16503(P)	Hit	LIN-IC	Motorsteuerung/Motor Control	14-DIP		-	-
HA 16603 FP	Hit	LIN-IC	=HA 16603P: SMD	16-MDIP		-	-
HA 16603 P	Hit	LIN-IC	Münz-Sensor/Coin Sensor, Contactless Switch	16-DIP		-	-
HA 16605 W	Hit	LIN-IC	Burner Controller	20-DIP		-	-
HA 16613 A	Hit	A/D-IC	8 Bit, Dual Slope, Ucc=+5V	28-DIP		-	-
HA 16617 P	Hit	LIN-IC	FLT Display Drv, 8 Segm., CMOS/TLL compatible	18-DIP		-	-
HA 16619 P	Hit	LIN-IC	FLT Display Drv, 8 Segm., CMOS/TLL compatible	18-DIP		-	-
HA 16628 P	Hit	LIN+D/A-IC	5 Bit, Position Amp. (f. DC Motor), Ucc=12V	16-DIP		-	-
HA 16629 P	Hit	LIN-IC	Tachometer F/V-Converter (f. DC Motor), Ucc=12V	16-DIP		-	-
HA 16631 MP	Hit	LIN-IC	=HA 16631P: SMD	18-MP		-	-
HA 16631 P	Hit	LIN-IC	FDD, Leseverst./Read Amp., Ucc=5/12V	18-DIP		-	KA 6201
HA 16632 AP	Hit	LIN-IC	FDD, VCO, Data Separate, Ucc=5V	28-DIP		-	-
HA 16636 AP	Hit	LIN-IC	Fehlstrom-/Ground Fault Interrupter	8-SIP		-	-
HA 16640 NT	Hit	BiMOS-IC	FDD, Schreib-/Write/Mechanism Controller,UDD=5/12V	42-SDIP		-	-
HA 16642 MP	Hit	LIN-IC	=HA 16642NT: SMD	44-MP		-	-
HA 16642 NT	Hit	LIN-IC	FDD, Schreib-Lese/Read-Write Processor, Ucc=5/12V	42-SDIP		-	-
HA 16643 MP	Hit	BiMOS-IC	SMD, FDD, Mechanik-/Mechanism Controller, Ucc=5V	44-MP		-	-
HA 16650 MP	Hit	BiMOS-IC	SMD, FDD, Mechanik-/Mechanism Controller, Ucc=5V	44-MP		-	-
HA 16651 MP	Hit	LIN-IC	SMD, FDD, Schreib-Lese/Read-Write Proc., Ucc=5/12V	44-MP		-	-
HA 16652 MP	Hit	LIN-IC	SMD, HDD, Schreib-Lese/Read-Write Prozessor, 5/12V	28-MP		-	-
HA 16652 P4	Hit	LIN-IC	HDD, Schreib-Lese/Read-Write Prozessor, Ucc=5/12V	22-DIP		-	-
HA 16652 P6	Hit	LIN-IC	HDD, Schreib-Lese/Read-Write Prozessor, Ucc=5/12V	28-DIP		-	-
HA 16654 AFP	Hit	LIN-IC	=HA 16654APS: SMD	14-MDIP		-	-
HA 16654 APS	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, 100...500kHz	8-DIP		-	-
HA 16656 MP	Hit	LIN-IC	SMD, HDD, Lese-/Read Pulse Generator, Ucc=5/12V	44-MP		-	-
HA 16658 MA,MP	Hit	LIN-IC	=HA 16658NT: SMD	44-MP		-	-
HA 16658 NT	Hit	LIN-IC	HDD, VCO, Read Data (MFM, RLL), Ucc=5V	42-SDIP		-	-
HA 16662 MP	Hit	LIN-IC	SMD, HDD, Interface(ST-506), Ucc=5V	44-MP		-	-
HA 16663 MP	Hit	LIN-IC	SMD, HDD, Lese-/Read Pulse Generator, Ucc=5/12V	18-MP		-	-

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International
HA 16664 AFP	Hit	LIN-IC	=HA 16664APS: SMD	14-MDIP			-
HA 16664 APS	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, 100...200kHz	8-DIP			-
HA 16666 FP	Hit	LIN-IC	=HA 16666P: SMD	16-MDIP			-
HA 16666 P	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, ...600kHz	8-DIP			-
HA 16670 MP	Hit	LIN-IC	SMD, HDD, Position Signal Generator, Ucc=5/12V	44-MP			-
HA 16671 MP	Hit	LIN-IC	SMD, HDD, VCM Servo Controller, 8Bit DAC, Ucc=5/12V	44-MP			-
HA 16672 MP	Hit	LIN-IC	SMD, HDD, VCM Servo Controller, 8Bit DAC, Ucc=5/12V	44-MP			-
HA 16676 MP	Hit	LIN-IC	SMD, HDD, Lese-/Read Pulse Generator, Ucc=5/12V	44-MP			-
HA 16681 MA,MP	Hit	LIN-IC	SMD, FDD, Schreib-Lese/Read-Write Proc., Ucc=5/12V	44-MP			-
HA 16682 MP	Hit	LIN-IC	SMD, HDD, Interface(ST-506), Ucc=5V	44-MP			-
HA 16686 MA,MP	Hit	LIN-IC	SMD, HDD, Lese-/Read Pulse Generator, Ucc=5/12V	44-MP			-
HA 16688 MP	Hit	LIN-IC	SMD, HDD, Schreib-Lese/Read-Write Proc., Ucc=5/12V	44-MP			-
HA 16689 MP	Hit	LIN-IC	SMD, HDD, Schreib-Lese/Read-Write Proc., Ucc=5/12V	44-MP			-
HA 16697 MP	Hit	LIN-IC	SMD, FDD, Schreib-Lese/Read-Write Proc., Ucc=5/12V	44-MP			-
HA 16721 MP	Hit	LIN-IC	SMD, FLT Display Drv, 32 Segm., TTL compatible	44-MP			-
HA 16722 MP	Hit	LIN-IC	SMD, FLT Display Drv, 32 Segm., TTL compatible	44-MP			-
HA 17008 RFP	Hit	D/A-IC	=HA 17008RG,RP: SMD	16-MDIP			-
HA 17008 RG,RP	Hit	D/A-IC	8 Bit, Multiplying, Ucc=15V, 85ns	16-DIC,DIP			-
HA 17012 G,P(B,C)	Hit	D/A-IC	12 Bit, Multiplying, Ucc=±15V, 250ns	20-DIC,DIP			-
HA 17080(A)GS	Hit	OP-IC	=HA 17080(A)PS: -40...+85°	8-DIC			TL 080...
HA 17080(A)PS	Hit	OP-IC	J-FET, Serie 080, ±18V, 13V/µs, -20...+75°, A=>CMR	8-DIP			TL 080...
HA 17082(A)GS,PS	Hit	OP-IC	=HA 17080... Dual	8-DIP,DIC			TL 082...
HA 17083(A)G,P	Hit	OP-IC	=HA 17080... Dual	14-DIP,DIC			TL 083...
HA 17084(A)G,P	Hit	OP-IC	=HA 17080... Quad	14-DIP,DIC			TL 084...
HA 17301 G	Hit	OP-IC	=HA 17301P: -40...+85°	14-DIC			-
HA 17301 G,P	Hit	OP-IC	Quad, +28V, 50mA, 2,6MHz, 0,2V/µs, -20...+75°	14-DIP			MC 3301
HA 17324 F,FP	Hit	OP-IC	=HA 17324(G,P): SMD	14-MDIP			... 124... 224... 324... 2902...
HA 17324(G,P)	Hit	OP-IC	Quad, Serie 124, ±16V, 50mA, 0,19V/µs, -20...+75°	14-DIC,DIP	(LM 324 N) ¹⁶	14-DIP	... 124... 224... 324... 2902...
HA 17339	Hit	KOP-IC	Quad, Serie 139, ±18V, 20mA, -20...+75°	14-DIP	(LM 339 N) ¹⁶	14-DIP	... 139... 239... 339... 2901...
HA 17339 F	Hit	KOP-IC	=HA 17339: SMD	14-MDIP			... 139... 239... 339... 2901...
HA 17358	Hit	OP-IC	Dual, Serie 158, ±16V, 50mA, 0,2V/µs, -20...+75°	8-DIP	(4558/8-D) ¹⁶	8-DIP	... 158... 258... 358... 1458...
HA 17358 F	Hit	OP-IC	=HA 17358: SMD	8-MDIP			... 158... 258... 358... 1458...
HA 17384 (B)FP	Hit	LIN-IC	=HA 17384PS: SMD	14-MDIP			-
HA 17384(A,B)PS	Hit	LIN-IC	PWM Schaltreg/Sw. Reg., Current Mode, ...300kHz	8-DIP			-
HA 17385(B)FP	Hit	LIN-IC	=HA 17384PS: SMD	14-MDIP			-
HA 17385 PS	Hit	LIN-IC	PWM Schaltreg/Sw. Reg., Current Mode, ...300kHz	8-DIP			-
HA 17393	Hit	KOP-IC	Dual, Serie 193, ±18V, -20...+75°	8-DIP	(LM 393/8-D) ¹⁶	8-DIP	... 193... 293... 393... 2903...
HA 17393 F	Hit	KOP-IC	=HA 17393: SMD	8-MDIP			... 193... 293... 393... 2903...
HA 17408 G,P	Hit	D/A-IC	8 Bit, Multiplying, Ucc=5V, 250ns	16-DIC,DIP			-
HA 17431 FP,FP(A,J)	Hit	Ref-Z-IC	=HA 17431P...: Fig. →	8-MDIP			µPC 1093G
HA 17431 P,PA,PJ	Hit	Ref-Z-IC	+2,5...40V, 1...100mA, Uref=2,495V(±0,1V), A=±0,055V	7(KARef)	TO-92L		TA 76431S, µPC 1093J
HA 17431PS,PSA,PSJ	Hit	Ref-Z-IC	=HA 17431P...: Fig. →	8-DIP			-
HA 17431 UA,UPA	Hit	Ref-Z-IC	=HA 17431P...: Fig. →	39(KARef)	SOT-89		TA 76431F, µPC 1093T
HA 17451 AP	Hit	LIN-IC	=HA 17451P: ohne/without Latch Circuits	16-DIP			-
HA 17451 FPA,FP	Hit	LIN-IC	=HA 17451(A)P: SMD	16-MDIP			-
HA 17451 P	Hit	LIN-IC	Dual, PWM Schaltreg/Sw. Reg., 3,3...40V, ...300kHz	16-DIP			-
HA 17458 F,FP,FPJ	Hit	OP-IC	=HA 17458GS,PS: SMD	8-MDIP			... 1458... 1558... 4558...
HA 17458 GS,PS	Hit	OP-IC	Dual, Serie 158, ±18V, 0,6V/µs, -25...+75°	8-DIC/DIP	(4558/8-D)	8-DIP	... 1458... 1558... 4558...
HA 17458 M	Hit	OP-IC	=HA 17458GS,PS: Fig. →	TO-99			... 1458... 1558... 4558...
HA 17458 PSJ	Hit	OP-IC	=HA 17458GS,PS: -40...+85°	8-DIP	(4558/8-D) ¹⁶	8-DIP	... 1558...
HA 17474(G,P,RP)	Hit	OP-IC	Quad, ±20V, 1,9V/µs, -20...+75°	14-DIC,DIP			(... 124... 224... 324... 2902...)
HA 17524 FP	Hit	LIN-IC	=HA 17524G,P: SMD	16-MDIP			SG 3524CD
HA 17524 G,P	Hit	LIN-IC	PWM Schaltregler/Switching Regulator, 450kHz	16-DIC,DIP			KA 3524, LM 3524, SG 3524, UC 3524A
HA 17555(GS,PS)(J)	Hit	LIN-IC	=NE 555, 0...+70°, GS,PS=-20...+75°, PSJ=-40...+85°	8-DIC,DIP		8-DIP	-NE 555
HA 17558(GS,PS)	Hit	OP-IC	Dual, ±18V, 1V/µs, -20...+75°	8-DIC,DIP			(... 1458... 1558... 4558...)
HA 17558 F,FP,FPJ	Hit	OP-IC	=HA 17558...: SMD	8-MDIP			(... 1458... 1558... 4558...)
HA 17558 PSJ	Hit	OP-IC	=HA 17558(GS,PS): -40...+85°	8-DIP			(... 1558...)
HA 17592(G,P)	Hit	LIN-IC	Differential Video-Verst./Amp., ...90MHz, Ucc=6V	14-DIC,DIP			-
HA 17711	Hit	KOP-IC	Dual	14-DIP			-
HA 17715 G	Hit	OP-IC	=HA 17715M: Fig. →	14-DIC			µA 715
HA 17715 M	Hit	OP-IC	hi-speed, Serie 115, ±18V, 6V/µs, 65MHz, -25...+75°	TO-100			µA 715
HA 17723 F	Hit	Z-IC	=HA 17723M: SMD, 0...+70°	14-MDIP			... 723...
HA 17723(G,P)	Hit	Z-IC	=HA 17723M: 0...+70°, G=-25...+75°	14-DIC,DIP	723/14-D	14-DIP	... 723...
HA 17723 M	Hit	Z-IC	+2...37V, 0,15A, -25...+70	TO-100	723/TO	TO-100	... 723...
HA 17733 M	Hit	LIN-IC	Differential Video-Verst./Amp., ...120MHz, Ucc=6V	TO-100			LM 733... µA 733...
HA 17733(G,P)	Hit	LIN-IC	=HA 17733M: Fig. →	14-DIP			KA 733... LM 733... µA 733...
HA 17741 G	Hit	OP-IC	Uni, Serie 741, ±18, 1V/µs, -20...+75°	14-DIC			... 741...
HA 17741(GS,PS)	Hit	OP-IC	=HA 17741G: Fig. →	8-DIC,DIP	(741/8-D) ¹⁶	8-DIP	... 741...
HA 17741 M	Hit	OP-IC	=HA 17741G: Fig. →	TO-99	(741/TO) ¹⁶	TO-99	... 741...
HA 17741 PSJ	Hit	OP-IC	=HA 17741G: -40...+85°	8-DIP			... 741...
HA 17747(G,P)	Hit	OP-IC	Dual, Serie 747, ±18V, 1V/µs, -20...+75°	14-DIC,DIP	(747/14-D) ¹⁶	14-DIP	... 747...
HA 17747 M	Hit	OP-IC	=HA 17747G: Fig. →	TO-100			... 747...
HA 17805P,V,VP,VPJ	Hit	Z-IC	+5V, 1A	17b	TO-220	7805/TO-220	17b ... 7805... (TO-220)
HA 17806P,V,VP,VPJ	Hit	Z-IC	+6V, 1A	17b	TO-220	7806/TO-220	17b ... 7806... (TO-220)
HA 17807P,V,VP,VPJ	Hit	Z-IC	+7V, 1A	17b	TO-220		17b ... 7807... (TO-220)
HA 17808P,V,VP,VPJ	Hit	Z-IC	+8V, 1A	17b	TO-220	7808/TO-220	17b ... 7808... (TO-220)
HA 17809P,V,VP,VPJ	Hit	Z-IC	+9V, 1A	17b	TO-220	7809/TO-220	17b ... 7809... (TO-220)
HA 17810P,V,VP,VPJ	Hit	Z-IC	+10V, 1A	17b	TO-220	7810/TO-220	17b ... 7810... (TO-220)
HA 17812P,V,VP,VPJ	Hit	Z-IC	+12V, 1A	17b	TO-220	7812/TO-220	17b ... 7812... (TO-220)
HA 17815P,V,VP,VPJ	Hit	Z-IC	+15V, 1A	17b	TO-220	7815/TO-220	17b ... 7815... (TO-220)
HA 17818P,V,VP,VPJ	Hit	Z-IC	+18V, 1A	17b	TO-220	7818/TO-220	17b ... 7818... (TO-220)
HA 17824P,V,VP,VPJ	Hit	Z-IC	+24V, 1A	17b	TO-220	7824/TO-220	17b ... 7824... (TO-220)
HA 17885P,V,VP,VPJ	Hit	Z-IC	+8,5V, 1A	17b	TO-220		17b ... 7885... (TO-220)
HA 178xx FM,FMP	Hit	Z-IC	=HA 17805...17885: Iso	17b	TO-220 Iso		17b ... 78xx... (TO-220 Iso)
HA 17901(P)	Hit	KOP-IC	Quad, Serie 139, ±18V, 20mA, -20...+75°	14-DIP	(LM 339 N) ¹⁶	14-DIP	... 139... 239... 339... 2901...
HA 17901 FP,FPJ,RP	Hit	KOP-IC	=HA 17901(P,PJ): SMD	14-MDIP			... 139... 239... 339... 2901...
HA 17901 G,PJ	Hit	KOP-IC	=HA 17901(P): -40...+85°	14-DIC,DIP			... 139... 239... 2901...
HA 17902(P)	Hit	OP-IC	Quad, Serie 124, 28V, 50mA, 0,19V/µs, -20...+75°	14-DIP	(LM 324 N) ¹⁶	14-DIP	... 124... 224... 2902...
HA 17902 FP,FPJ	Hit	OP-IC	=HA 17902(P,PJ): SMD	14-MDIP			... 124... 224... 2902...
HA 17902 G,PJ	Hit	OP-IC	=HA 17902(P): -40...+85°	14-DIC,DIP			... 124... 224... 2902...
HA 17903(PS)	Hit	KOP-IC	Dual, Serie 193, ±18V, -20...+75°	8-DIP	(LM 393/8-D) ¹⁶	8-DIP	... 193... 293... 393... 2903...
HA 17903 FP,FPJ	Hit	KOP-IC	=HA 17903(PS,PSJ): SMD	8-MDIP			... 193... 293... 393... 2903...
HA 17903 G,PSJ	Hit	KOP-IC	=HA 17903(PS): -40...+85°	8-DIC,DIP			... 193... 293... 2903...

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
HA 17904 FP,FPJ	Hit	OP-IC	=HA 17904PS,PSJ: SMD	8-MDIP			... 158... 258... 358... 2904...	
HA 17904 GS	Hit	OP-IC	=HA 17904PS,PSJ: -40...+85°	8-DIP			... 158... 258... 2904...	
HA 17904 (PS)	Hit	OP-IC	Dual, Serie 158, ±16V, 50mA, 0.2V/µs, -20...+75°	8-DIP			... 158... 258... 358... 2904...	
HA 17904 PSJ	Hit	OP-IC	=HA 17904PS: -40...+85°	8-DIP			... 158... 258... 2904...	
HA 17905 FM,FMP	Hit	Z-IC	Iso, -5V, 1A	17c	TO-220 Iso	(7905/TO-220) ³	17c	... 7905... (TO-220 Iso)
HA 17906 FM,FMP	Hit	Z-IC	Iso, -6V, 1A	17c	TO-220 Iso			... 7906... (TO-220 Iso)
HA 17908 FM,FMP	Hit	Z-IC	Iso, -8V, 1A	17c	TO-220 Iso			... 7908... (TO-220 Iso)
HA 17909 FM,FMP	Hit	Z-IC	Iso, -9V, 1A	17c	TO-220 Iso			... 7909... (TO-220 Iso)
HA 17910 FM,FMP	Hit	Z-IC	Iso, -10V, 1A	17c	TO-220 Iso			... 7910... (TO-220 Iso)
HA 17912 FM,FMP	Hit	Z-IC	Iso, -12V, 1A	17c	TO-220 Iso	(7912/TO-220) ³	17c	... 7912... (TO-220 Iso)
HA 17915 FM,FMP	Hit	Z-IC	Iso, -15V, 1A	17c	TO-220 Iso	(7915/TO-220) ³	17c	... 7915... (TO-220 Iso)
HA 17952 FM,FMP	Hit	Z-IC	Iso, -5.2V, 1A	17c	TO-220 Iso			... 7952... (TO-220 Iso)
HA 19202	Hit	A/D-IC	4 Bit, Ucc=5V, 10MHz	22-DIP				-
HA 19203 MP	Hit	A/D-IC	4 Bit, Ucc=5V, 10MHz	18-MP				-
HA 19209 C,TP	Hit	A/D-IC	8 Bit Flash, VC, hi-speed, lo-power, Ucc=+5V,30MHz	28-DIP,DIP				-
HA 19209 MP	Hit	A/D-IC	=HA 19209C,TP: SMD	44-MP				-
HA 19210 C,TP	Hit	A/D-IC	8 Bit Flash, VC, hi-speed, lo-power, Ucc=+5V,30MHz	28-DIP,DIP				-
HA 19210 MP	Hit	A/D-IC	=HA 19210C,TP: SMD	44-MP				-
HA 19211(B)MP	Hit	A/D-IC	=HA 19211(B)P: SMD	44-MP				-
HA 19211(B)NT	Hit	A/D-IC	=HA 19211(B)P:	30-SDIP				-
HA 19211 P	Hit	A/D-IC	8 Bit Flash, VC, hi-speed, lo-power, Ucc=+5V,30MHz	28-DIP				-
HA 19212 MP	Hit	A/D-IC	=HA 19212P: SMD	44-MP				-
HA 19212 NT	Hit	A/D-IC	=HA 19212P:	30-SDIP				-
HA 19212 P	Hit	A/D-IC	8 Bit Flash, VC, hi-speed, lo-power, Ucc=+5V,30MHz	28-DIP				-
HA 19213 MP	Hit	A/D-IC	=HA 19213NT: SMD	28-MP				-
HA 19213 NT	Hit	A/D-IC	7 Bit Flash, hi-speed, lo-power, Ucc=+5V, 30MHz	30-SDIP				-
HA 19214 NT	Hit	A/D-IC	10 Bit Flash, VC,hi-speed, lo-power, Ucc=±5V,20MHz	42-SDIP				-
HA 19216 (C)	Hit	A/D-IC	6 Bit Flash, hi-speed, Ucc=+5V, 30MHz	18-DIP,DIC				-
HA 19216 MP	Hit	A/D-IC	=HA 19216(C): SMD	28-MP				-
HA 19503 ANT	Hit	D/A-IC	6 Bit, Clock Generator, Ucc=+5V	30-SDIP				-
HA 19505	Hit	D/A-IC	10 Bit, Ucc=+5V, 50MHz	20-DIP				-
HA 19507 MP	Hit	D/A-IC	=HA 19507NT: SMD	28-MP				-
HA 19507 NT	Hit	D/A-IC	6 Bit, Clock Generator, Ucc=+5V	30-SDIP				-
HA 19508 A	Hit	D/A-IC	6 Bit, Ucc=+5V, 30MHz	16-DIP				-
HA 19508 AMP	Hit	D/A-IC	=HA 19508A: SMD	18-MP				-
HA 19510 A	Hit	D/A-IC	8 Bit Flash, hi-speed, lo-power, Ucc=+5V, 50MHz	18-DIP				-
HA 19510 AMP	Hit	D/A-IC	=HA 19510A: SMD	18-MP				-
HA 21001 MS	Hit	GaAs-IC	VHF/UHF Tuner, Ucc=8...10V	18-MP				-
HA 21008	Hit	GaAs-IC	BS Tuner, 0.95...2.05GHz, Ucc=4.5...5.5V	44	SOT-143			-
HA 21009 MS	Hit	GaAs-IC	BS Tuner, 0.95...2.05GHz, Ucc=4.5...5.5V	18-MP				-
HA 21010 MS	Hit	GaAs-IC	BS Tuner, 0.95...1.35GHz, Ucc=4.5...5.5V	18-MP				-
HA 118001 MP	Hit	LIN-IC	VC, FM Signal Processor	44-MP				-
HA 118002 FP	Hit	LIN-IC	Camera, Vorverst./Pre-Amp.	16-MDIP				-
HA 118003 MP	Hit	LIN-IC	=HA 118003NT: SMD	28-MP				-
HA 118003 NT	Hit	LIN-IC	Camera, Matrix-Verstärker/Amplifier	22-SDIP				-
HA 118010 MP	Hit	LIN-IC	Camera, 4-Kanal/Channel Processor	44-MP				-
HA 118019 NT	Hit	LIN-IC	VC, 4 Kopf-Vorverst./4-Head Pre-Amplifier	30-SDIP				-
HA 118041 NT	Hit	LIN-IC	VC, 2 Kopf-Vorverst./2-Head Pre-Amplifier	22-SDIP				-
HA 118058	Hit	LIN-IC	VC, Digital-Schalter/Switch	16-DIP				-
HA 118059	Hit	LIN-IC	VC(S-VHS), 3x Video-Schalter/Switch, Ucc=5V	16-DIP				-
HA 118059 FP	Hit	LIN-IC	=HA 118059: SMD	16-MDIP				-
HA 118070	Hit	LIN-IC	VC, Video-Schalter/Switch, Ucc=5V	8-DIP				-
HA 118070 FP	Hit	LIN-IC	=HA 118070: SMD	8-MDIP				-
HA 118082 MA	Hit	LIN-IC	Camera, 4-Kanal/Channel Processor	44-MP				-
HA 118084	Hit	LIN-IC	VC(VHS, S-VHS), Signal Processor, FM AGC	18-DIP				-
HA 118084 MP	Hit	LIN-IC	=HA 118084: SMD	18-MP				-
HA 118088	Hit	LIN-IC	VC, PIP Processor	22-SDIP				-
HA 118088 MP	Hit	LIN-IC	=HA 118088: SMD	28-MP				-
HA 118099	Hit	LIN-IC	VC(S-VHS), 3x Video-Schalter/Switch, Ucc=5V	16-DIP				-
HA 118099 FP	Hit	LIN-IC	=HA 118099: SMD	16-MDIP				-
HA 118104	Hit	LIN-IC	VC, 3x Video-Schalter/Switch, Ucc=5V	16-DIP				-
HA 118104 FP	Hit	LIN-IC	=HA 118104: SMD	16-MDIP				-
HA 118105 MA	Hit	LIN-IC	=HA 118105NT: SMD	56-MP				-
HA 118105(D)NT	Hit	LIN-IC	VC, 1-Chip VHS Processor	56-SDIP				-
HA 118118 MA	Hit	LIN-IC	Camera, Weissbalance/White Balance	44-MP				-
HA 118120 AMA	Hit	LIN-IC	Camera, Signal Processor	44-MP				-
HA 118121 FP,VFP	Hit	LIN-IC	SMD, Camera, EVF (Electronic View Finder)	16-MDIP				-
HA 118124 MA	Hit	LIN-IC	VC(VHS, S-VHS), Signal Processor	56-MP				-
HA 118129 MP	Hit	LIN-IC	FM IF, AGC, AFC, 430MHz	28-MP				-
HA 118142 AMA	Hit	LIN-IC	Camera, 4-Kanal/Channel Processor	44-MP				-
HA 118144 AF	Hit	LIN-IC	Camera, Signal Processor	48-MP				-
HA 118162 NT	Hit	LIN-IC	VC(S-VHS), 4 Kopf-Vorverst./4-Head Pre-Amplifier	30-SDIP				-
HA 118191 NT	Hit	LIN-IC	VC(VHS), 4 Kopf-Vorverst./4-Head Pre-Amplifier	30-SDIP				-
HA 118285 BF	Hit	LIN-IC	=HA 118285BNT: SMD	56-MP				-
HA 118285 BNT	Hit	LIN-IC	VC(VHS), Multistandard Processor	56-SDIP				-
HA 166008 FP	Hit	LIN-IC	=HA 166008MP:	24-MDIP				-
HA 166008 MP	Hit	LIN-IC	SMD, HDD, Schreib-Lese/Read-Write Proc., Ucc=5/12V	28-MP				-
HA 166009 MP	Hit	LIN-IC	SMD, HDD, Schreib-Lese/Read-Write Proc., Ucc=5/12V	28-MP				-
HA 166010 MP	Hit	LIN-IC	SMD, HDD, Schreib-Lese/Read-Write Proc., Ucc=5/12V	44-MP				-
HA 166024 FP	Hit	LIN-IC	SMD, HDD, Schreib-Lese/Read-Write Proc., Ucc=5V	16-MDIP				-
HA 166025 FP	Hit	LIN-IC	SMD, HDD, Schreib-Lese/Read-Write Proc., Ucc=5V	20-MDIP				-
HB....HZ								
HB		Si-N	=2SC3120 (SMD-Marking)	35	SOT-23			-2SC3120
HB		Si-N	=2SC3137 (Marking)	25	SOT-103			-2SC3137
HB		Si-N	=2SC4245 (SMD-Marking)	35(2mm)	SOT-323			-2SC4245
HB		Si-N	=2SD1464-HB (SMD-Marking)	39	SOT-89			-2SD1464
HB(s)		Si-N	=BFN 22 (SMD-Marking)	35	SOT-23			-BFN 22
HB		GaAs-FET	=CFY 75-13 (SMD-Marking)	44	SOT-143			-
HB		GaAs-N-FET-d	=CFY 65-14 (Marking)	51	SOT-173			-CFY 55
HBF 4000....4xxx	Sgs	CMOS-Logic	=HEF					-
HC		Si-N	=2SC2733 (SMD-Marking)	35	SOT-23			-2SC2733
HC		Si-N	=2SC3121 (SMD-Marking)	35	SOT-23			-2SC3121

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International
HC		Si-N	=2SC4246 (SMD-Marking)	35(2mm)	SOT-323		+2SC4246
HC		Si-N	=2SC4463 (SMD-Marking)	35(2mm)	SOT-323		+2SC4463
HC(s)		Si-P	=BFN 23 (SMD-Marking)	35	SOT-23		+BFN 23
HC		GaAs-FET	=CFY 75-15 (SMD-Marking)	44	SOT-143		-
HC 1 A3M...L20	Nec	Si-N+R	=AC 1A3M...L20: SMD	39b	SOT-89		-
HC 2000 H	Rca	Hybrid-IC	Op-Amp., 75V, 7A, PQ=100W(eff)				-
HC 2500	Rca	Hybrid-IC	Op-Amp., 75V, 7A, PQ=100W(eff)				-
HC 16701	Hit	LIN-IC	Thermal Head Driver, Ucc=5V, 0,1A	Chip			-
HD		Si-N	=2SC3122 (SMD-Marking)	35	SOT-23		+2SC3122
HD		Si-N	=2SC4249 (SMD-Marking)	35(2mm)	SOT-323		+2SC4249
HD 1 A3M...L3N	Nec	Si-N+R	=AD 1A3M...L3N: SMD	39b	SOT-89		-
HD 2 A3M...L3N	Nec	Si-N+R	=AD 2A3M...L3N: SMD	39b	SOT-89		-
HD 74 LSxx...	Hit	TTL-Logic	Standard TTL-Logic 74LS-Serie				... 74LSxx... (TTL)
HD 102		Si-N				BC 546	7a
HD 105		Si-N		22a	TO-66	BD 243 C	17j
HD 106		Si-N				BC 141	2a
HD 107		Si-P				BC 161	2a
HD 110		Si-P				BC 556	7a
HD 140		Si-P				BC 556	7a
HD 6350	Hit	I/O-IC	+KS 5824	24-DIP			KS 5824, MC 6850
HD 10551	Hit	LIN-IC	FM Frequ.-Teiler/Divider, 1:10...1:44	8-SIP			-
HD 14000...14xxx	Hit	CMOS-Logic	Standard CMOS-Logic 4000-Serie				... 4000...4xxx (CMOS)
HD 17903 GS/PS	Hit	KOP-IC	Dual	8-DIC/DIP			-LM 2903
HD 38980 C	Hit	MOS-IC	Alarmuhr/Digital Clock, FLT Drv	40-DIP			-
HD 38991 A	Hit	MOS-IC	Alarmuhr/Digital Clock, LED Drv	40-DIP			-
HD 42851	Hit	MOS-IC	CB PLL Synthesizer	24-DIP			-
HD 42853	Hit	MOS-IC	CB PLL Synthesizer	22-DIP			-
HD 42854	Hit	MOS-IC	CB Scanner f.Kanalwahl/Channel Select	16/20-DIP			-
HD 42855	Hit	MOS-IC	CB Scanner f.Kanalwahl/Channel Select	16/20-DIP			-
HD 43880	Hit	MOS-IC	Analoguhr/Analog Clock (4MHz)	8-DIP			-
HD 43890	Hit	CMOS-IC	Tischuhr/Desk-top Clock	8-DIP			-
HD 44007(A)	Hit	CMOS-IC	Camera, Color Signal Processor (NTSC/PAL/SECAM)	28-DIP			-
HD 44015	Hit	LIN-IC	PLL Frequ. Synthesizer f. Digital Tuning	22-DIP			-
HD 44231 P	Hit	CMOS-IC	Telecom, A-Law Codec, Filter (Sync)	16-DIP			MB 6026A
HD 44232 P	Hit	CMOS-IC	Telecom, µ-Law Codec, Filter (Sync)	16-DIP			MB 6025A
HD 44235 C	Hit	CMOS-IC	Telecom, A-Law Codec, Filter (Sync)	16-DIP			MB 6056A
HD 44236 C	Hit	CMOS-IC	Telecom, µ-Law Codec, Filter (Sync)	16-DIP			MB 6055A
HD 44273 P	Hit	CMOS-IC	Telecom, A-Law Codec, Filter (Sync/Async)	16-DIP			MB 6022A
HD 44274 P	Hit	CMOS-IC	Telecom, µ-Law Codec, Filter (Sync/Async)	16-DIP			MB 6021A
HD 44277 P	Hit	CMOS-IC	Telecom, A-Law Codec, Filter (Sync/Async)	16-DIP			MB 6052A
HD 44278 P	Hit	CMOS-IC	Telecom, µ-Law Codec, Filter (Sync/Async)	16-DIP			MB 6051A
HD 44752	Hit	LIN-IC	PLL Frequ. Synthesizer Controller (AM/FM)	42-DIP			-
HD 44840		LIN-IC					-
HD 49201 A	Hit	MOS-IC	CD, Signal Processor, Udd=5V	80-MP			-
HD 49202 NT	Hit	CMOS-IC	CD, Digital Audio-Filter, Udd=5V	30-SDIP			-
HD 49211 BFS	Hit	CMOS-IC	R-DAT, Signal Prozessor, RAM/Converter Ctrl.	100-MP			-
HD 49212	Hit	CMOS-IC	R-DAT, Digital Servo, µComp. Interface	80-MP			-
HD 49215	Hit	MOS-IC	CD, Signal Processor, µComp. Interface, D/A Ctrl.	80-MP			-
HD 49217 AFS	Hit	MOS-IC	CD-ROM, Signal Processor, Double Speed Support	100-MP			-
HD 49226 AFS	Hit	CMOS-IC	R-DAT, Signal Processor, µComp.Interface, RAM Ctrl	100-MP			-
HD 49228 FS	Hit	CMOS-IC	R-DAT, Digital Servo, µComp. Interface	80-MP			-
HD 49229	Hit	CMOS-IC	R-DAT, Data Extractor, Clock Generator	56-MP			-
HD 49232 FS	Hit	MOS-IC	CD, Digital Signal Processor, µComp. Interface	80-MP			-
HD 49233 AFS	Hit	MOS-IC	CD, Signal Processor, µComp. Interface, RAM, DAC	80-MP			-
HD 49303	Hit	CMOS-A/D-IC	8 Bit, TV/VC, hi-speed, lo-power, Udd=+5V, 20MHz	30-DIP			-
HD 49304(ANT)	Hit	CMOS-D/A-IC	TV, 8 Bit, 3 Channel, Udd=+5V, 50MHz	42-SDIP			-
HD 49306 AF	Hit	CMOS-A/D-IC	TV, 9 Bit, Udd=+5V	48-MP			-
HD 49307	Hit	CMOS-D/A-IC	TV, 8 Bit, 3 Channel, Udd=+5V, >30MHz	56-MP			-
HD 49315 F	Hit	CMOS-A/D-IC	VC, Camera, 10 Bit, Digital Video	48-MP			-
HD 49409 FS	Hit	LIN-IC	TV,VC, PIP Control, A/D-D/A Converter	100-MP			-
HD 49412 FS	Hit	LIN-IC	TV,VC, PIP Control (NTSC), A/D-D/A Converter	100-MP			-
HD 49417 AFS	Hit	LIN-IC	TV,VC, MUSE Decoder	100-MP			-
HD 49420 FS	Hit	LIN-IC	TV,VC, PIP Control (NTSC), A/D-D/A Converter	80-MP			-
HD 49421 FS	Hit	LIN-IC	TV,VC, PIP Control (NTSC), A/D-D/A Converter	80-MP			-
HD 49704 FP	Hit	CMOS-IC	VC, VHS-C, Servo-Controller	80-MP			-
HD 49723	Hit	LIN-IC					KA 8307
HD 49733 NT	Hit	CMOS-IC	VC, Servo-Controller	56-SDIP			-
HD 49740 NT	Hit	MOS-IC	VC, ON-Screen Display	42-SDIP			-
HD 49741 NT	Hit	CMOS-IC	VC, Servo-Controller	56-SDIP			-
HD 49748	Hit	CMOS-IC	+KA 8316	56-SDIP			KA 8316
HD 49781 F	Hit	CMOS-IC	=HD 49781NT: SMD	56-MP			-
HD 49781 NT	Hit	CMOS-IC	VC, Servo-Controller	56-SDIP			-
HD 49783 FP	Hit	CMOS-IC	=HD 49783NT: SMD	16-MDIP			-
HD 49783 NT	Hit	CMOS-IC	VC, Synchronized Serial Bus	16-DIP			-
HD 49801 FB	Hit	CMOS-IC	Camera, Digital Signal Processor	100-MP			-
HD 61927	Hit	MOS-IC	Camera, Color Signal (NTSC)	22-DIP			-
HD 64951	Hit	BiMOS-I/O-IC	µComp., SCSI Interface	68-MP			-
HD 64961	Hit	CMOS-I/O-IC	µComp., SCSI Controller				-
HD 153007	Hit	MOS-IC	Min, HDD, 2-7 Code Encoder/Decoder	44-MP			-
HD 153009	Hit	MOS-IC	Min, HDD, 2-7 Code Encoder/Decoder	44-MP			-
HD 153011	Hit	MOS-IC	Min, HDD, 2-7 RLL Encoder/Decoder	44-MP			-
HD 153013	Hit	MOS-IC	Min, HDD, 2-7 Code Encoder/Decoder	44-MP			-
HD 153510 F50.F135	Hit	D/A-IC	8 Bit, 3 Kanal/Channel, 50/135MHz	56-MP			-
HD 431115	Hit	MOS-IC	Analoguhr/analogue clock (4MHz)	8-DIP			-
HD 440072	Hit	CMOS-IC	Camera, Color Signal Processor (NTSC/PAL/SECAM)	28-DIP			-
HDA-0505...-2415	Shi	Hybrid-IC	DC-DC Converter	=7-SIP	(22x40mm)		-
HDB-0505...-2415	Shi	Hybrid-IC	DC-DC Converter	=7-SIP	(25x45mm)		-
HDF-0515...-4815	Shi	Hybrid-IC	DC-DC Converter	=7-SIP	(45x21mm)		-
HE		Si-N	=2SC3123 (SMD-Marking)	35	SOT-23		+2SC3123
HE		Si-N	=2SC4250 (SMD-Marking)	35(2mm)	SOT-323		+2SC4250
HEF 4000...4xxx	Phi	CMOS-Logic	Standard CMOS-Logic 4000-Serie				... 4000...4xxx (CMOS)

Original	Fabric.	Constr.	Info	(Compl. Fig.	JAEGER	Fig.	International	
HEF 4750 VD	Phi	MOS-IC	VHF/UHF Frequ.-Synthesizer, >1GHz	28-DIC			-	
HEF 4751 VD	Phi	MOS-IC	=HEF 4751VP: Keramik	28-DIC			-	
HEF 4751 VP	Phi	MOS-IC	Frequ.-Teiler/Divider f. HEF 4750	28-DIP			-	
HEF 4751 VT	Phi	MOS-IC	=HEF 4751VP: SMD	28-MDIP			-	
HF		Si-N	=2SC2805 (Marking)	25	SOT-103		+2SC2805	
HF		Si-N	=2SC3124 (SMD-Marking)	35	SOT-23		+2SC4251	
HF		Si-N	=2SC4251 (SMD-Marking)	35(2mm)	SOT-323		+2SC4251	
HF		Si-P	=BFN 23 (SMD-Marking)	35	SOT-23		+BFN 23	
HF		Si-N	=KTC 3882 (SMD-Marking)	35	SOT-23		+KTC 3882	
HFSD-1 A....Z	Sak	Si-Di	FRr. 200...1000V, 0,3A, Uf<1,2V(0,5A), <800ns HFSD-1=400V, A=600V, B=800V, C=1000C, Z=200V	31a	(6x11mm0)	BA 159	31a	BA 157...159, BY 204/..., BY 208/..., ++
HG		Si-N	=2SC2806 (Marking)	25	SOT-103		+2SC2806	
HG		Si-N	=2SC3439-G (SMD-Marking)	39	SOT-89		+2SC3439	
HGE 122...24005	Shi	Hybrid-IC	DC-DC Converter	Module			-	
HGF 051...12001	Shi	Hybrid-IC	DC-DC Converter	Module			-	
HGG 122...24005	Shi	Hybrid-IC	DC-DC Converter	Module			-	
HH		Si-N	=2SC4253 (SMD-Marking)	35(2mm)	SOT-323		+2SC4253	
HH		Si-N	=2SC3125 (SMD-Marking)	35	SOT-23		+2SC3125	
HH		Si-N	=2SC3439-H (SMD-Marking)	39	SOT-89		+2SC3439	
HH		Si-N	=KTC 3881 (SMD-Marking)	35	SOT-23		+KTC 3881	
HH 8090 B	Mat	Hybrid-IC	Schaltregler/Switching Regulator	=10-SIP			-	
HH 8360	Mat	Hybrid-IC	8-Bit D/A-Converter	=13-SIL			-	
HI		Si-N	=2SC4247 (SMD-Marking)	35(2mm)	SOT-323		+2SC4247	
HI		MOS-N-FET-d	=3SK188 (SMD-Marking)	44	SOT-143		+3SK188	
HIT 5609...5610		Si-N/P	=CS 5609...5610			+CS 5609-5610		
HIT 9010...9022		Si-N/P	=CS 9010...9022			+CS 9010-9022		
HJ		Si-N	=2SC3439-J (SMD-Marking)	39	SOT-89		+2SC3439	
HJ		Si-N	=2SC3602 (Marking)	25	SOT-103		+2SC3602	
HK		Si-N	=2SC3828 (SMD-Marking)	44	SOT-143		+2SC3828	
HK		Si-N	=2SD1006-HK (SMD-Marking)	39	SOT-89		+2SD1006	
HKZ 101(S)	Sie	LIN-IC	Hall-IC, Magnet-Gabelschranke/Vane Switch				-	
HKZ 121	Sie	LIN-IC	Hall-IC, Magnet-Gabelschranke/Vane Switch				-	
HL		Si-P	=2SA1502 (SMD-Marking)	35	SOT-23		+2SA1502	
HL		Si-P	=2SA1722 (SMD-Marking)	35(2mm)	SOT-323		+2SA1722	
HL		Si-N	=2SC3862 (SMD-Marking)	35	SOT-23		+2SC3862	
HL		Si-N	=2SD1006-HL (SMD-Marking)	39	SOT-89		+2SD1006	
HLD 00006...05003	Shi	Hybrid-IC	DC-DC Converter	Module			-	
HLE 00006...12003	Shi	Hybrid-IC	DC-DC Converter	Module			-	
HM		Si-N	=2SC3547B (SMD-Marking)	35	SOT-23		+2SC3547B	
HM		Si-N	=2SC4248 (SMD-Marking)	35(2mm)	SOT-323		+2SC4248	
HM		Si-N	=2SD1006-HM (SMD-Marking)	39	SOT-89		+2SD1006	
HM 6514		sRAM-IC	1k x 4 Bit				US 224D20	
HM 53051 FP-...	Hit	CMOS-RAM-IC	=HM 53051P: SMD	28-MDIP			-	
HM 53051 P-...	Hit	CMOS-RAM-IC	TV,VC, 262144x4 Bit, Frame Memory, 34, 45, 60ns	18-DIP			-	
HM 53461 JP-...	Hit	CMOS-VRAM-IC	=HN 53461P: SMD		24-MDIP		-	
HM 53461 P-...	Hit	CMOS-VRAM-IC	TV,VC, 65536x4 Bit, Multiport Video RAM,100...150ns		24-DIP		-	
HM 53461 ZP-...	Hit	CMOS-VRAM-IC	=HN 53461P: Fig. →		24-SOP		-	
HM 53462 JP-...	Hit	CMOS-VRAM-IC	=HN 53462P: SMD		24-MDIP		-	
HM 53462 P-...	Hit	CMOS-VRAM-IC	TV,VC, 65536x4 Bit, Multiport Video RAM,100...150ns		24-DIP		-	
HM 53462 ZP-...	Hit	CMOS-VRAM-IC	=HN 53462P: Fig. →		24-SOP		-	
HM 63021 FP-...	Hit	RAM-IC	=HM 63021P: SMD	28-MDIP			-	
HM 63021 P-...	Hit	RAM-IC	TV,VC, 2048x8 Bit, Line Memory, 28, 34, 45ns	28-DIP			-	
HM 530281 TT-...	Hit	CMOS-RAM-IC	TV,VC, 331776x8 Bit, Frame Memory,20, 25, 34, 45ns	44-SMDIP			-	
HM 530283 FP-...	Hit	CMOS-RAM-IC	TV,VC, 331776x8 Bit, Frame Memory,20, 25, 34, 45ns	32-MDIP			-	
HN		Si-N	=2SC4214 (SMD-Marking)	44	SOT-143		+2SC4214	
HN		Si-N	=2SC4244 (SMD-Marking)	35(2mm)	SOT-323		+2SC4244	
HN 1 A01F	Tos	Si-P	SMD, Dual, 50/50V, 0,15A, >80MHz	46	SOT-163		-	
HN 1 A01FU	Tos	Si-P	=HN 1 A01F:	46(2mm)	SOT-363		-	
HN 1 B01F	Tos	Si-N/P	SMD, NPN+PNP, 60/50+50/50V, 0,15A, 150+120MHz	46	SOT-163		-	
HN 1 B01FU	Tos	Si-N/P	=HN 1 B01F:	46(2mm)	SOT-363		-	
HN 1 C01F	Tos	Si-N	SMD, Dual, 60/50V, 0,15A, >80MHz	46	SOT-163		-	
HN 1 C01FU	Tos	Si-N	=HN 1 C01F:	46(2mm)	SOT-363		-	
HN 1 C03F	Tos	Si-N	SMD, Dual, 50/20V, hi-Ueb=25V, 0,3A, 30MHz	46	SOT-163		-	
HN 1 C03FU	Tos	Si-N	=HN 1 C03F:	46(2mm)	SOT-363		-	
HN 2 A01FU	Tos	Si-P	SMD, Dual, 50/50V, 0,15A, >80MHz	46(2mm)	SOT-363		-	
HN 2 C01FU	Tos	Si-N	SMD, Dual, 60/50V, 0,15A, >80MHz	46(2mm)	SOT-363		-	
HN 3 B01F	Tos	Si-P/N	SMD, PNP+PNP, 60/50+50/50V, 0,15A, 150+120MHz	46	SOT-163		-	
HN 3 C01F	Tos	Si-N	SMD, Dual, VHF, 30/20V, 50mA, 1400MHz	46	SOT-163		-	
HN 3 C02F	Tos	Si-N	SMD, Dual, UHF, 30/15V, 50mA, 2400MHz	46	SOT-163		-	
HN 3 C03F	Tos	Si-N	SMD, Dual, UHF, 20/12V, 30mA, 4000MHz	46	SOT-163		-	
HN 3 C06F	Tos	Si-N	SMD, Dual, UHF, 20/12V, 80mA, 7000MHz, F<2dB(1GHz)	46	SOT-163		-	
HN 3 C07F	Tos	Si-N	SMD, Dual, UHF, 20/10V, 40mA, 10GHz, F=1,7dB(2GHz)	46	SOT-163		-	
HN 3 C08F	Tos	Si-N	SMD, Dual, UHF, 20/10V, 15mA, 10GHz, F=1,8dB(2GHz)	46	SOT-163		-	
HN 3 G01J	Tos	N-FET+Si-N	SMD, N-FET(20V)+NPN-Trans(60/50V, 0,15A)	45	SOT-153		-	
HO		Si-P	=2SA1203-O (SMD-Marking)	39	SOT-89		+2SA1203	
HO		Si-P	=KTA1663-O (SMD-Marking)	39	SOT-89		+KTA 1663	
HP		Si-P	=2SA1036-HP (SMD-Marking)	=35	(MMT)		+2SA1036	
HP		Si-P	=2SA1036K-P (SMD-Marking)	35	SOT-23		+2SA1036K	
HP		Si-P	=2SA1577-P (SMD-Marking)	35(2mm)	SOT-323		+2SA1577	
HP		Si-N	=2SC4527 (SMD-Marking)	35	SOT-23		+2SC4527	
HP		Si-N	=2SD1007-HP (SMD-Marking)	39	SOT-89		+2SD1007	
HP 5082-4657		Opto					-	
HPA 72 R	Say	Si-N+Di	HA, 1500/800, 7/16A, 60W, sat<5V(4A)	18c	TO-3P Iso	BU 508DF	16c	BU 508DF, 2SC3892A, 2SC4123...24, 2SD2251
HPA 100 R	Say	Si-N	HA, hi-def, 1500/800V, 10/25A, 150W, sat<5V(6A)	77j	TOP-3L			2SC3995, 2SC4288A
HPA 150 R	Say	Si-N	HA, hi-def, 1500/800V, 15/35A, 150W, sat<5V(10A)	77j	TOP-3L			2SC3996, 2SC4289A
HPG 8	Gie	Si-Di	kV-Rr, 8kV, 0,05A	31a	(47x5x6)			1N5184
HPG 10	Gie	Si-Di	=HPG 8: 10kV, 0,04A	31a	(47x5x6)			1N5184
HPG 15	Gie	Si-Di	=HPG 8: 15kV, 0,03A	31a	(47x5x6)			1N3054
HPG 20	Gie	Si-Di	=HPG 8: 20kV, 0,02A	31a	(47x5x6)			1N3056
HQ		Si-P	=2SA1036-HQ (SMD-Marking)	=35	(MMT)			+2SA1036
HQ		Si-P	=2SA1036K-Q (SMD-Marking)	35	SOT-23			+2SA1036K
HQ		Si-P	=2SA1577-Q (SMD-Marking)	35(2mm)	SOT-323			+2SA1577

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
HQ		Si-P	=2SB956-Q (SMD-Marking)	39	SOT-89		-2SB956	
HQ		Si-N	=2SC3928-Q (SMD-Marking)	35	SOT-23		-2SC3928	
HQ		Si-N	=2SC4155-Q (SMD-Marking)	35(2mm)	SOT-323		-2SC4155	
HQ		Si-N	=2SD1007-HQ (SMD-Marking)	39	SOT-89		-2SD1007	
HQ 1 A3M...L3N	Nec	Si-P+R	=AQ 1A3M...L3N: SMD	39b	SOT-89		-	
HR		Si-P	=2SA1035-R (SMD-Marking)	35	SOT-23		-2SA1035	
HR		Si-P	=2SA1036-HR (SMD-Marking)	=35	(MMT)		-2SA1036	
HR		Si-P	=2SA1036K-R (SMD-Marking)	35	SOT-23		-2SA1036K	
HR		Si-P	=2SA1531A-R (SMD-Marking)	35(2mm)	SOT-323		-2SA1531A	
HR		Si-P	=2SA1577-R (SMD-Marking)	35(2mm)	SOT-323		-2SA1577	
HR		Si-P	=2SB956-R (SMD-Marking)	39	SOT-89		-2SB956	
HR		Si-N	=2SC3928-R (SMD-Marking)	35	SOT-23		-2SC3928	
HR		Si-N	=2SC4155-R (SMD-Marking)	35(2mm)	SOT-323		-2SC4155	
HR		Si-N	=2SD1007-HR (SMD-Marking)	39	SOT-89		-2SD1007	
HR 1 A3M...L3N	Nec	Si-P+R	=AR 1A3M...L3N: SMD	39b	SOT-89		-	
HR 5 A B	Hit	Si-Di	Rr. Uni. A=100, B=200V, 0.4/3A, Uf<1,1V(0,4A)	31a	DO-39	BA 159	31a	BA 157...159, BY 204/..., BY 208/..., ++
HR 51....		Si-Di	=1N4001...4007			1N4007	31a	-1N4001...4007
HR 100(R)	Tho	Si-Di	Rr. Uni. 100V, 3A, Uf<1V(3A), R: <3µs	31a	DO-27A	RGP 30 M	31a	BY 251...255, GP 30B...M, 1N5401...08, ++
HR 200(R)	Tho	Si-Di	=HR 100: 200V	31a	DO-27A	RGP 30 M	31a	BY 251...255, GP 30D...M, 1N5402...08, ++
HR 400(R)	Tho	Si-Di	=HR 100: 400V	31a	DO-27A	RGP 30 M	31a	BY 252...255, GP 30G...M, 1N5404...08, ++
HR 400(R)		Si-Di	=BYX 71/350	26	SOD-38	BY 329/1200 ⁺	17k	-BYX 71/350
HR 600(R)	Tho	Si-Di	=HR 100: 600V	31a	DO-27A	RGP 30 M	31a	BY 253...255, GP 30J...M, 1N5406...08, ++
HR 800(R)	Tho	Si-Di	=HR 100: 800V	31a	DO-27A	RGP 30 M	31a	BY 254...255, GP 30K...M, 1N5407...08, ++
HR 1000(R)	Tho	Si-Di	=HR 100: 1000V	31a	DO-27A	RGP 30 M	31a	BY 255, GP 30M, MR 510, 1N5408, ++
HS		Si-P	=2SA1035-S (SMD-Marking)	35	SOT-23			-2SA1035
HS		Si-P	=2SA1531A-S (SMD-Marking)	35(2mm)	SOT-323			-2SA1531A
HS		Si-P	=2SB956-S (SMD-Marking)	39	SOT-89			-2SB956
HS		Si-N	=2SC3928-S (SMD-Marking)	35	SOT-23			-2SC3928
HS		Si-N	=2SC4155-S (SMD-Marking)	35(2mm)	SOT-323			-2SC4155
HS		Si-N	=2SD2540 (SMD-Marking)	39	SOT-89			-2SD2540
HS 15		Se-Di	=TV 11					TV 11
HS 5305...5308(A)	Gen	Si-N	=2N5305...5308(A): 0.9W	7c°	TO-92+Clip			-2N5305...5308(A)
HS 5810...5823	Gen	Si-N/P	=2N5810...5823: 0.7W	7a°	TO-92+Clip			-2N5810...5823
HS 6010...6017	Gen	Si-N/P	=2N6010...6017: 0.7W	7a°	TO-92+Clip			-2N6010...6017
HS 6018...6021	Gen	Si-N	=2N6018...6021: 0.7W	7a°	TO-92+Clip			-2N6018...6021
HSG 3020...3250	Sgs	CMOS-IC	HCMOS Gate Arrays					-
HSG 5080...5600	Sgs	CMOS-IC	HCMOS Gate Arrays					-
HT		Si-P	=2SA1035-T (SMD-Marking)	35	SOT-23			-2SA1035
HT		Si-P	=2SA1531A-T (SMD-Marking)	35(2mm)	SOT-323			-2SA1531A
HT		Si-P	=2SB956-T (SMD-Marking)	39	SOT-89			-2SB956
HT		Si-N	=2SC3928-T (SMD-Marking)	35	SOT-23			-2SC3928
HT		Si-N	=2SC4155-T (SMD-Marking)	35(2mm)	SOT-323			-2SC4155
HT 2	Fer	Si-N	SMD, Uni. 90V, 0.1A, 0.3W, <500/2000ns	35a	SOT-23			2SC4050
HT 3	Fer	Si-P	SMD, Uni. 90V, 0.1A, 0.3W, <500/1000ns	35a	SOT-23			2SA1566
HV 10		Si-Di	=BA 127	31a		1N4148	31a	-BA 127
HV 13		Si-Di	=BA 127	31a		1N4148	31a	-BA 127
HV 15	Hit	Ge-St	10mA, 0.15W, Uf=0,145V(1,5mA)	2	TO-1			-
HV 16	Hit	Ge-St	10mA, 0.25W, Uf=0,145V(2,3mA)	2	TO-1			-
HV 17(C)	Hit	Ge-St	20mA, 0.5W, Uf=0,145V(3,5mA)	2	TO-1			-
HV 18	Hit	Ge-St	10mA, 0.1W, Uf=0,145V(1mA)	2	TO-1			-
HV 23 D,E,F	Hit	Si-St	20V, 50mA, Uf=0.66...0.8V(3mA) D=0.66...0.75V, E=0.73...0.9V, F=0.66...0.8V	9c	(6x6x3,5)	(1N4148)	31a	BA 216, BA 314
HV 23 G	Hit	Si-St	3V, 10mA, Uf=0.58...0.69V(3mA)	31a	DO-35	(1N4148)	31a	BA 216, BA 314
HV 25		Si-Di	=BA 127	31a		1N4148	31a	-BA 127
HV 26	Hit	Si-St	200mA, Uf=0.68...0.75V(30mA)	31a		(1N4148)	31a	BA 220, BZ 102/0V7, BZX 55/C0V8
HV 46		C-Di	=BA 102	31a				-BA 102
HV 46(RD)	Hit	Si-St	3V, 10mA, Uf=1,17...1,4V(3mA)	31a		Z-Diode 1,4V	31a	BZV 86/1V4, BZX 75/C1V4, ZTE 1.5
HV 70	Hit	Si-St	5V, 50mA, 0.25W, Uf=0.61...0.81V(0.5mA)	31a	DO-35	(1N4148)	31a	BA 216, BA 314
HV 75	Hit	Si-St	2.5V, 1A, Uf=0.77...0.87V(100mA)	31a	DO-41			BZV 22/C1, ZPY 1
HV 80	Hit	Si-St	10V, 50mA, 0.25W, Uf=0.55...0.75V(3mA)	31a	DO-35	(1N4148)	31a	BA 216, BA 314...315
HV 100	Hit	Si-St	100V, 0.38W, Uf=70...115V(1mA)	31a	(6x14mm0)			-
HVG 1	Gie	Si-Di	kV-Rr. 1kV, 0.3A, Uf<3V(1A), 2µs	31a	SOD-57			GP 02-20, MR 250-2, 1N1732(A)
HVG 2	Gie	Si-Di	=HVG 1: 2kV, 0.3A	31a	SOD-57			GP 02-20, MR 250-2, 1N1732(A)
HVG 3	Gie	Si-Di	=HVG 1: 3kV, 0.25A, Uf<4V(1A)	31a	SOD-57			GP 02-30, MR 250-3, 1N1733(A)
HVG 4	Gie	Si-Di	=HVG 1: 4kV, 0.2A, Uf<6V(1A)	31a	SOD-57			GP 02-40, MR 250-4, 1N1734(A)
HVG 5	Gie	Si-Di	=HVG 1: 5kV, 0.15A, Uf<8V(1A)	31a	SOD-57			MR 250-5, 1N1734(A)
HVT 15(SS)	Sak	Si-Di	kV-Rr. 11kV, 15mA, Uf<32V(10mA)	31a	(12x4mm0)	(BY 713)	31a	HS 10
HVT 18	Sak	Si-Di	kV-Rr. 12kV, 15mA	31a	(16x5,50)	(BY 713)	31a	HS 10
HVT 20(SS)	Sak	Si-Di	kV-Rr. 14kV, 15mA, Uf<42V(10mA)	31a	(12x4mm0)	(BY 713)	31a	HS 13
HVT 22	Sak	Si-Di	kV-Rr. 14kV, 15mA, Uf<25V(10mA)	31a	(16x5,50)	(BY 713)	31a	HS 13
HVT 25(SS)	Sak	Si-Di	kV-Rr. 17kV, 15mA, Uf<52V(10mA)	31a	(12x4mm0)	BY 713	31a	HS 13
HVT 30(E,S,SS)	Sak	Si-Di	kV-Rr. 18...24kV, 10mA, Uf<75V(10mA)	31a	(15x4mm0)	(BY 713)	31a	-
HX		Si-P	=2SB1572-HX (SMD-Marking)	39	SOT-89			-2SB1572
HY		Si-P	=2SA1203-Y (SMD-Marking)	39	SOT-89			-2SA1203
HY		Si-P	=2SB1572-HY (SMD-Marking)	39	SOT-89			-2SB1572
HY		Si-P	=KTA1663-Y (SMD-Marking)	39	SOT-89			-KTA 1663
HYB 4116 A-3	Sie	dRAM-IC	16384x1 Bit, 200ns	16-DIP				...4116....
HYB 4116 A-4	Sie	dRAM-IC	=HYB 4116A-3: 250ns	16-DIP				...4116....
HYB 4116-P2	Sie	dRAM-IC	16384x1 Bit, 150ns	16-DIP				...4116....
HYB 4116-P3	Sie	dRAM-IC	=HYB 4116-P2: 200ns	16-DIP				...4116....
HYB 4116 -P4,P-4	Sie	dRAM-IC	=HYB 4116-P2: 250ns	16-DIP				...4116....
HYB 4164-P1	Sie	dRAM-IC	65536x1 Bit, 120ns	16-DIP				...4164....
HYB 4164-P2	Sie	dRAM-IC	=HYB 4164-P1: 150ns	16-DIP				...4164....
HYB 4164-P3	Sie	dRAM-IC	=HYB 4164-P1: 200ns	16-DIP				...4164....
HYB 41256-12	Sie	dRAM-IC	262144x1 Bit, 120ns	16-DIP				...41256....
HYB 41256-15	Sie	dRAM-IC	=HYB 41256-12: 150ns	16-DIP				...41256....
HYB 41256-20	Sie	dRAM-IC	=HYB 41256-12: 200ns	16-DIP				...41256....
HYB 511000-12	Sie	dRAM-IC	=HYB 511000-10: 120ns	18-DIP				...41024....
HYB 511000-10	Sie	dRAM-IC	1048576x1 Bit, 100ns, page mode	18-DIP				...41024....
HZ		Si-P	=2SB1572-HZ (SMD-Marking)	39	SOT-89			-2SB1572
HZ 1 C3	Hit	Z-Di	1.5...1.7V(5mA), 0.5W	31a	DO-35			-

Original	Fabric.	Constr.	Info	{Compl. Fig.	JAEGER	Fig.	International	
HZ 2...36(H)...	Hit	Z-Di	2...36V, 0.5W, A=-15...-7%, B=-10...0%, C=-2...+8%, (A,B,C)1,2,3: engere Toleranzen/tighter tolerances	31a	DO-35	Z-Diode ...V	31a	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...+
HZ 2.7...39E(B1...4)	Hit	Z-Di	2.7...39V, 0.5W, B1=-8...-4%, B2=-5...-1%, B3=-2...+3% B4=-1...+3%	31a	DO-35	Z-Diode ...V	31a	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...+
HZ 6...36(...L)	Hit	Z-Di	In 6...36V, 0.4W, A=-12...-6%, B=-8...0%, C=0...+8% (A,B,C)1,2,3L: engere Toleranzen/tighter toleranc.	31a	DO-35	(Z-Diode ...V)	31a	BZV 39/..., 1N4099...4122
HZ 2...5(A,B,C)LL	Hit	Z-Di	In 2...5V, 0.25W, A=-10...0%, B=±5%, C=0...+10%	31a	DO-35	(Z-Diode ...V)	31a	BZV 39/..., 1N4615...25
HZ 2.0...36(B,C)P	Hit	Z-Di	2.0...36V, 0.8W, BP=-6...+6%, CP=0...+12%	31a	DO-41	Z-Diode ...V	31a	BZV 85/..., BZX 22/..., BZX 61/..., ZPY...+
HZF 2.0...36(B,C)P	Hit	Z-Di	=HZ 2.0...36(B,C)P: SMD, 0.9W	71a(5mm)				BZG 03-..., MA 1Z..., PTZ..., RD...FM
HZK 2...36 A,B,C	Hit	Z-Di	=HZ 2...36(H)A,B,C: SMD, 0.5W	72a(3,4mm)	SOD-80	Z-Di ...V(SMD)	72a(3,4mm)	BZD 277/..., BZV 55/..., RLZ...(J)
HZK 6...36(A,B,C)L	Hit	Z-Di	=HZ 6...36(A,B,C)L: SMD, 0.4W	72a(3,4mm)	SOD-80	Z-Di ...V(SMD)	72a(3,4mm)	-
HZK 2...5(A,B,C)LL	Hit	Z-Di	=HZ 2...5(A,B,C)LL: SMD, 0.25W	72a(3,4mm)	SOD-80			-
HZM 2.0...36N(B...)	Hit	Z-Di	SMD, 2.0...36V, B=-5...+5%, B1=-5...-1%, B2=-3...-2% B3=+1...+5%	35p	SOT-23			BZX 84/... RD...M
HZS 2...36	Hit	Z-Di	=HZ 2...36(H)...: 0,4W	31a	DO-34	-HZ 2...36(H)		+HZ 2...36(H)...
HZS 2.7...39E...	Hit	Z-Di	=HZ 2.7...39E...: 0,4W	31a	DO-34	-HZ 2.7...39E...		+HZ 2.7...39E...
HZS 5.6...36J(B...)	Hit	Z-Di	5.6...36V, 0.4W, B1=-6...-1%, B2=±2.5%, B3=0...+5%	31a	DO-34	Z-Diode ...V	31a	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...+
HZS 6...36 L...	Hit	Z-Di	=HZ 6...36L...: 0,4W	31a	DO-34	-HZ 6...36L...		+HZ 6...36L...
HZS 2...5 LL...	Hit	Z-Di	=HZ 2...5LL...: 0,25W	31a	DO-34	-HZ 2...5LL...		+HZ 2...5LL...
HZS 2.0...39N(B...)	Hit	Z-Di	2.0...39V, 0.4W, B1=-8...-4%, B2=-5...0%, B3=-2...+3% B4=-2...+1%	31a	DO-35	Z-Diode ...V	31a	BZV 85/..., BZX 55/..., BZX 83/..., ZPD...+
HZS 5.6...36S...	Hit	Z-Di	=HZS 5.6...36J...: 0,4W	31a	DO-34	-HZS 5.6...36J		+HZS 5.6...36J...
HZT 33	Hit	Z-IC, Ref-Di	Tuner Stabi, 31...35V, 20mA, 0.4W, ±1mV/°C(=ZTK 33)	31h		ZTK 33	31h	+ZTK 33
HZU 2.0...36...	Hit	Z-Di	=HZM 2.0...36N...:	71a(1,7mm)	SOD-323			DTZ ... RD...S
I								
I		GaAs-N-FET	=2SK1196 (Marking)	51	SOT-173			+2SK1196
I C		Si-N+R	=UN 7231 (SMD-Marking)	39	SOT-89			+UN 7231
I 9		Si-Di	=1SS336 (SMD-Marking)	35	SOT-23			+1SS336
i 1103	Int	dRAM-IC	1024 Bit		18-DIP			U 253D
i 1302	Int	ROM-IC	2048 Bit		24-DIP			U 501D
i 1602 A	Int	PROM-IC	256x8 Bit		24-DIP			U 551D
i 1702 A	Int	EPROM-IC	256x8 Bit		24-DIP			U 552C
i 2102 A	Int	sRAM-IC	1024 Bit		16-DIP			U 202D
i 2114	Int	sRAM-IC	1024x4 Bit		18-DIP			... 2114..., U 214D
i 2115	Int	sRAM-IC	1024x1 Bit		16-DIP			U 215D
i 2124	Int	sRAM-IC	1024x4 Bit		18-DIP			U 224D, UL 224D, US 224D, VL 224D
i 2125	Int	sRAM-IC	1024x1 Bit		16-DIP			U 225D
i 2147 H	Int	sRAM-IC	4096x1 Bit		18-DIP			... 2147...
i 2148	Int	sRAM-IC	1024x4 Bit		18-DIP			... 2148..., U 2148C
i 2308	Int	ROM-IC	8192-Bit, mask.-progr.		24-DIP			U 505D
i 2364	Int	ROM-IC	8192x8 Bit		28-DIP			MN 2364, U 2364D
i 2616	Int	PROM-IC	2048x8 Bit		24-DIP			U 2616D
i 2708	Int	EPROM-IC	1024x8 Bit		24-DIP			U 555C
i 2716	Int	EPROM-IC	2048x8 Bit		24-DIP			... 2716..., U 2716C
i 2764	Int	EPROM-IC	8192x8 Bit, 200ns		28-DIP			... 2764...
i 3245	Int	I/O-IC	=µA 9645					+µA 9645
i 4016	Int	sRAM-IC	2048x8 Bit		24-DIP			MN 4216, MN 4316
i 8008	Int	µP-IC	8-Bit-CPU		18-DIP			U 808D
i 8205	Int	TTL-IC	Schottky, 1/8-Binärdecoder/Binary Decoder		16-DIP			DS 8205D
i 8212	Int	TTL-IC	Schottky, 8-Bit Bustreiber/Bus Driver		24-DIP			DS 8212D
i 8216	Int	TTL-IC	Schottky, 4-Bit Bustreiber/Bus Driver		16-DIP			DS 8216D
i 8272	Int	I/O-IC	Floppy Disk Controller		40-DIP			U 8272D
i 8282	Int	TTL-IC	Schottky, 8-Bit Bustreiber/Bus Driver		20-DIP			DS 8282D
i 8283	Int	TTL-IC	Schottky, 8-Bit Bustreiber/Bus Driver		20-DIP			DS 8283D
i 8286	Int	TTL-IC	Schottky, 8-Bit Bustreiber/Bus Driver		20-DIP			DS 8286D
i 8287	Int	TTL-IC	Schottky, 8-Bit Bustreiber/Bus Driver		20-DIP			DS 8287D
i 23128	Int	ROM-IC	16384x8 Bit, 250ns		28-DIP			MN 23128
i 82720	Int	MOS-IC	Grafic Display Controller					U 82720D
IA		MOS-N-FET-e	=µPA602T (SMD-Marking)	46	SOT-163			+µPA602T
IBB 1488 B		OP-IC	Dual, Serie 158		8-DIP	4558/8-D	8-DIP	+MC 1458
IC		Si-N	=2SC3016 (SMD-Marking)	35	SOT-23			+2SC3016
ICL 108...	Isi	OP-IC	+µA 108...					+µA 108...
ICL 741...	Isi	OP-IC	+µA 741...					+µA 741...
ICL 7106	Tsc	A/D-IC	A/D-Converter, 3,5 digit					TSC 7106A
ICL 7136	Sie	A/D-IC	3,5-Digit A/D-Converter		40-DIP			C 7136D
ICL 7650 CPD	Isi	CMOS-OP-IC	Chopperstabilisiert, ±9V		14-DIP			U 7650 DD
ICL 7660 CAP	Isi	CMOS-IC	Spannungswandler/volt. conv., 0...+70°		8-DIP			U 7660 DC
ICL 7660 CSA	Isi	CMOS-IC	=ICL 7660CAP: -25...+85°		8-DIP			U 7660 DG
ICM 7555 CD	Phi	LIN-IC	=NE 555: CMOS-Version, SMD, 0...+70°		8-MDIP			-
ICM 7555 CFE,CN	Phi	CMOS-IC	=NE 555: CMOS-Version, 0...+70°		8-DIC/DIP			KS 555N
ICM 7555 ID	Phi	LIN-IC	=NE 555: CMOS-Version, SMD, -40...+85°		8-MDIP			-
ICM 7555 IFE,IN	Phi	LIN-IC	=NE 555: CMOS-Version, -40...+85°		8-DIP			-
ICM 7555 MFE,MN	Phi	LIN-IC	=NE 555: CMOS-Version, -55...+125°		8-DIC/DIP			-
ICM 7556		CMOS-IC	=KS 556N		14-DIP			KS 556N
ID		Si-N	=2SC3127 (SMD-Marking)	35	SOT-23			+2SC3127
IE		Si-N	=2SC3722K-E (SMD-Marking)	35	SOT-23			+2SC3722K
IFB		Si-P	=2SB973-B (SMD-Marking)	35	SOT-23			+2SB973
IFC		Si-P	=2SB973-C (SMD-Marking)	35	SOT-23			+2SB973
IGD		MOS-N-FET-d	=2SK1215-D (SMD-Marking)	35(2mm)	SOT-323			+2SK1215
IGD		MOS-N-FET-d	=2SK360-D (SMD-Marking)	35	SOT-23			+2SK360
IGE		MOS-N-FET-d	=2SK1215-E (SMD-Marking)	35(2mm)	SOT-323			+2SK1215
IGE		MOS-N-FET-d	=2SK360-E (SMD-Marking)	35	SOT-23			+2SK360
IGF		MOS-N-FET-d	=2SK1215-F (SMD-Marking)	35(2mm)	SOT-323			+2SK1215
IGF		MOS-N-FET-d	=2SK360-F (SMD-Marking)	35	SOT-23			+2SK360
IGT 4 D/E10...11	Gen	MOS-N-IGBT	Iso-Gate, bipolar Tr., 400...500/25V, 18/40A, 75W	17(GCEC)	TO-220			-
IGT 6 D/E10...11	Gen	MOS-N-IGBT	=IGT 4 D/E10...11:	23(EGC)	TO-3			GT 25J101
IGT 6 D/E20...21	Gen	MOS-N-IGBT	Iso-Gate, bipolar Tr., 400...500V, 20/32A, 125W	23(EGC)	TO-3			GT 25J101
IGT 8 D/E20...21	Gen	MOS-N-IGBT	=IGT 6 D/E20...21:	16(GCEC)	TO-247			GT 25J101
IHC		N-FET	=2SK431-C (SMD-Marking)	35	SOT-23			+2SK431
IHD		N-FET	=2SK431-D (SMD-Marking)	35	SOT-23			+2SK431
IHE		N-FET	=2SK431-E (SMD-Marking)	35	SOT-23			+2SK431
IHF		N-FET	=2SK431-F (SMD-Marking)	35	SOT-23			+2SK431