

# BDY26B



**MECHANICAL DATA** 

Dimensions in mm (inches)





### HIGH CURRENT NPN SILICON TRANSISTOR

### FEATURES

- HIGH SWITCHING CURRENTS
- HIGH RELIABILITY
- CECC SCREENING OPTIONS
- SPACE QUALITY LEVELS OPTIONS
- JAN LEVEL SCREENING OPTIONS

### **APPLICATIONS**

- SWITCHING REGULATORS
- LINEAR APPLICATIONS

### TO3 (TO204AA)

Pin 1 = Base

Pin 2 = Emitter

Case = Collector

## **ABSOLUTE MAXIMUM RATINGS**

T <sub>CASE</sub> = 25 °C unless otherwise stated					
V <sub>CBO</sub>	Collector - Base Voltage		300V		
V <sub>CEO</sub>	Collector - Emitter Voltage		180V		
$V_{EBO}$	Emitter – Base Voltage	10V			
I <sub>C</sub>	Continuous Collector Current		6A		
I <sub>B</sub>	Base Current		3A		
P <sub>tot</sub>	Total Power Dissipation at	T <sub>case</sub> = 25 ℃	50W		
		Derate above 25℃	0.29 W/℃		
$T_J$	Junction Temperature		200 <i>°</i> C		
T <sub>stg</sub>	Storage Temperature		-65 to 200 <i>°</i> C		

Semelab Plc reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by Semelab is believed to be both accurate and reliable at the time of going to press. However Semelab assumes no responsibility for any errors or omissions discovered in its use. Semelab encourages customers to verify that datasheets are current before placing orders.

**Semelab plc.** Telephone +44(0)1455 556565. Fax +44(0)1455 552612. E-mail: <u>sales@semelab.co.uk</u> Website: <u>http://www.semelab.co.uk</u>



THER	MAL CHARACTERISTICS	Max	Unit
R <sub>th</sub> j-case	Thermal resistance to case	3.5	°C/W

#### **ELECTRICAL CHARACTERISTICS** (T<sub>case</sub>=25 °C unless otherwise stated)

	Parameter	Test Conditions		Min.	Тур.	Max.	Unit
I <sub>CEO</sub>	Collector Cut-Off Current	$V_{CE} = 140V$	$I_{\rm B} = 0$			1.0	
I <sub>CES</sub>	Collector Cut-Off Current	$V_{CE} = 180V$	$V_{BE} = 0$			1.0	mA
I <sub>EBO</sub>	Emitter Cut-Off Current	$V_{EB} = 10V$	$I_{\rm C} = 0$			1.0	
V <sub>(BR)CEO</sub> *	Collector-Emitter Breakdown Voltage	$I_{\rm C} = 50 {\rm mA}$	$I_{\rm B} = 0$	180			
V <sub>(BR)CBO</sub> *	Collector-Base Breakdown Voltage	$I_{\rm C} = 3mA$		300			V
V <sub>CE(sat)</sub> *	Collector-Emitter Saturation Voltage	$I_{\rm C} = 2.0 A$	$I_{\rm B} = 0.25 A$			0.6	v
V <sub>BE(sat)</sub> *	Base-Emitter Saturation Voltage	$I_{\rm C} = 2.0 A$	$I_{B} = 0.25A$			1.2	
h <sub>FE</sub> *	Forward-current transfer ratio	I <sub>C</sub> = 1.0A	$V_{CE} = 4.0V$		65		
		I <sub>C</sub> = 2.0A	$V_{CE} = 4.0V$	30	45	90	

### **DYNAMIC CHARACTERISTICS**

C <sub>obo</sub>	Output Capacitance	$I_E = 0$	$V_{CB} = 10V$		65	120	pF
		f = 1.0MHz					
FT	Transition Frequency	$I_{\rm C} = 0.5 A$	$V_{CE} = 15V$	10			MHz
		f = 10.0MHz		10			
T <sub>on</sub>	Turn-on time	I <sub>C</sub> = 5.0A	I <sub>B1</sub> = 1.0A			1.0	
T <sub>off</sub>	Turn-off time	I <sub>C</sub> = 5.0A	$I_{B1} = -I_{B2} = 1.0A$			3.5	μs

\* Pulse test  $t_p$  = 300µs,  $\delta$  < 2%

Semelab Plc reserves the right to change test conditions, parameter limits and package dimensions without notice. Information furnished by Semelab is believed to be both accurate and reliable at the time of going to press. However Semelab assumes no responsibility for any errors or omissions discovered in its use. Semelab encourages customers to verify that datasheets are current before placing orders.

**Semelab plc.** Telephone +44(0)1455 556565. Fax +44(0)1455 552612. E-mail: <u>sales@semelab.co.uk</u> Website: <u>http://www.semelab.co.uk</u>