

PC713V/PC714V

* Lead formmg type (I type) dnd taping reel type (P type) are also available (PC713VI/PC714VI/PC713VP/PC714VP) (Page 656)

*** TÜV (VDE0884) approved type is also available as an option.

■ Features

1. TTL compatible output
 2. Current transfer ratio
(CTR : MIN. 50% at $I_F = 5\text{mA}$, $V_{CE} = 5\text{V}$)
 3. Low collector dark current
(I_{CEO} : MAX. 10^{-7}A at $V_{CE} = 20\text{V}$)
 4. High isolation voltage between input and output (V_{iso} : $5\text{ }000\text{V}_{\text{rms}}$)
 5. Recognized by UL, file No. E64380

■ Applications

1. System appliances, measuring instruments
 2. Registers, copiers, automatic vending machines
 3. Electric home appliances such as fan heaters
 4. Medical instruments, physical and chemical equipment
 5. Signal transmission between circuits of different potentials and impedances

■ **Absolute** Maximum Ratings ($T_a = 25^\circ\text{C}$)

Parameter		Symbol	Rating	Unit
Input	Forward current	I_F	50	mA
	* Peak forward current	I_{FM}	1	A
	Reverse voltage	V_R	6	V
	Power dissipation	P	70	mW
	Collector-emitter voltage	V_{CEO}	35	V
	Emitter-collector voltage	V_{ECO}	6	V
Output	* Collector-base voltage	V_{CBO}	35	V
	Emitter-base voltage	V_{EBO}	6	V
	Collector current	I_C	50	mA
	Collector power dissipation	P_C	150	mW
	Total power dissipation	P_{tot}	170	mW
	* Isolation voltage	V_{IS90}	5000	V _{rms}
Operating temperature		T_{opr}	-25 to +100	°C
Storage temperature		T_{stg}	-40 to +125	°C
* Soldering temperature		T_s	260	°C

*1 Pulse width \leq 100 μ s Duty ratio = 0.001

*? Applies only to PC713W


*340 to 60%RH AC for 1 minute

*4 For 10 seconds


High Isolation Voltage Type, General Purpose Photocoupler

■ Outline Dimensions

(Unit : mm)



PC714V



■ Electro-optical Characteristics

(Ta = 25°C)

Parameter		Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Input	Forward voltage	V _F	I _F = 20mA	—	1.2	1.4	V
	Peak forward voltage	V _{FM}	I _{FM} = 0.5A	—	—	3.0	v
	Reverse current	I _R	V _R = 4V	—	—	10	μA
	Terminal capacitance	C _t	V = 0, f = 1kHz	—	30	250	pF
Output	Collector dark current	I _{CEO}	V _{CE} = 20V, I _F = 0, * ⁵ R _{BE} = ∞	—	—	10 ⁻⁷	A
Transfer characteristics	Current transfer ratio	CTR	I _F = 5mA, V _{CE} = 5V, * ⁵ R _{BE} = ∞	50	—	600	%
	Collector-emitter saturation voltage	V _{CE(sat)}	I _F = 20mA, I _C = 1mA, * ⁵ R _{BE} = ∞	—	0.1	0.2	V
	Isolation resistance	R _{ISO}	DC500V, 40 to 60%RH	5 × 10 ¹⁰	10 ¹¹	—	Ω
	Floating capacitance	C _f	V = 0, f = 1 MHz	—	0.6	1.0	pF
	Cut-off frequency	f _C	V _{CE} = 5V, I _C = 2mA, R _L = 100Ω, * ⁵ R _{BE} = ∞	—	80	—	kHz
	Response time	Rise time	V _{CE} = 2V, I _C = 2mA	—	4	18	μs
		Fall time	R _L = 100Ω, * ⁵ R _{BE} = ∞	—	3	18	μs

*5 Applies only to PC713V

*6 Classification table of current transfer ratio is shown below

Model No.	Rank mark	CTR(%)
PC713V1/PC714V1	A	80 to 160
PC713V2/PC714V2	B	130 to 260
PC713V3/PC714V3	c	200 to 400*
PC713V5/PC714V5	A or B	80 to 260
PC713V6/PC714V6	B or C	130 to 400
PC713V8/PC714V8	A, B or C	80 to 400
PC713V/PC714V	A, B, C or no marking	50 to 600

Measurement conditions



I_F = 5mAV_{CE} = 5VT_a = 25°C**Fig. 1 Forward Current vs. Ambient Temperature****Fig. 2 Collector Power Dissipation vs. Ambient Temperature**







Fig. 3 Peak Forward Current vs. Duty Ratio**Fig. 5 Current Transfer Ratio vs. Forward Current****Fig. 7 Relative Current Transfer Ratio vs. Ambient Temperature****Fig. 4 Forward Current vs. Forward Voltage****Fig. 6 Collector Current vs. Emitter Voltage****Fig. 8 Collector-emitter Saturation Voltage vs. Ambient Temperature**

Fig. 9 Collector Dark Current vs. Ambient Temperature




Fig.10 Collector-base Dark Current vs. Ambient Temperature




Fig.11 Response Time vs. Load Resistance






Fig.12 Frequency Response




Test Circuit for Response Time



(PC714V has no base terminal.)

Last Circuit for Frequency Response



(PC714V has no base terminal.)

- Please refer to the chapter "Precautions for Use" (Page 78 to 93)