

**CMOS Analog Switches****Features**

- $\pm 15\text{-V}$  Input Range
- Fast Switching— $t_{ON}$ : 110 ns
- Low  $r_{DS(on)}$ : 30  $\Omega$
- Single Supply Operation
- CMOS Logic Levels
- Micropower: 30 nW

**Benefits**

- Full Rail-to-Rail Analog Signal Range
- Low Signal Error
- Wide Dynamic Range
- Low Power Dissipation

**Applications**

- Low Level Switching Circuits
- Programmable Gain Amplifiers
- Portable and Battery Powered Systems


**Description**

The DG304A through DG307A series of monolithic CMOS switches were designed for applications in communications, instrumentation and process control. This series is well suited for applications requiring fast switching and nearly flat on-resistance over the entire analog range.

Designed on the Siliconix PLUS-40 CMOS process to achieve low power consumption and excellent on/off switch performance, these switches are ideal for

battery powered applications, without sacrificing switching speed. Break-before-make switching action is guaranteed, and an epitaxial layer prevents latchup. Single supply operation (for positive switch voltages) is allowed by connecting the V<sub>-</sub> rail to 0 V.

Each switch conducts equally well in both directions when on, and blocks up to the supply voltage when off. These switches are CMOS input compatible.

**Functional Block Diagram and Pin Configuration****Ordering Information – DG304A**

Temp Range	Package	Part Number
-55 to 125°C	14-Pin Plastic DIP	DG304ACJ
	14-Pin CerDIP	DG304AAK/883
		JM38510/11605BCA
	10-Pin Can	JM38510/11605BIA
	14-Pin Sidebraze	JM38510/11605BCC

**Truth Table**

Logic	Switch
0	OFF
1	ON

Logic "0"  $\leq 3.5\text{ V}$   
Logic "1"  $\geq 11\text{ V}$

Switches Shown for Logic "0" Input


# TEMIC

Siliconix

## DG304A/305A/306A/307A

### Functional Block Diagram and Pin Configuration (Cont'd)

#### DG305A



#### Ordering Information – DG305A

Temp Range	Package	Part Number
-55 to 125°C	14-Pin CerDIP	JM38510/11605BCA
	10-Pin Can	JM38510/11606BIC
	14-Pin Sidebraze	JM38510/11606BCA


#### Truth Table

Logic	SW <sub>1</sub>	SW <sub>2</sub>
0	OFF	ON
1	ON	OFF


Logic "0" ≤ 3.5 V  
Logic "1" ≥ 11 V

Switches Shown for Logic "0" Input

#### DG306A



## Functional Block Diagram and Pin Configuration (Cont'd)

**DG307A**

Four SPST Switches per Package

**Truth Table**

Logic	SW <sub>1</sub> , SW <sub>2</sub>	SW <sub>3</sub> , SW <sub>4</sub>
0	OFF	ON
1	ON	OFF

Logic "0" ≤ 3.5 V  
Logic "1" ≥ 11 V

Switches Shown for Logic "0" Input

**Ordering Information – 307A**

Temp Range	Package	Part Number
0 to 70°C	14-Pin Plastic DIP	DG307ACJ
–25 to 85°C		DG307ABK
		DG307AAK
		DG307AAK/883
–55 to 125°C		JM38510/11608BCA
	14-Pin Sidebraze	JM38510/11608BCC

**Absolute Maximum Ratings**

## Voltages Referenced to V-

V+ ..... 44 V

GND ..... 25 V

Digital Inputs<sup>a</sup>, V<sub>S</sub>, V<sub>D</sub> ..... (V-) – 2 V to (V+) + 2 V or  
30 mA, whichever occurs first

Current, Any Terminal ..... 30 mA

## Continuous Current, S or D

(Pulsed at 1 ms, 10% duty cycle max) ..... 100 mA

Storage Temperature (AAA, AAK, ABK Suffix) – 65 to 150°C  
(ACJ Suffix) ..... – 65 to 125°CPower Dissipation<sup>b</sup>14-Pin Plastic DIP<sup>c</sup> ..... 470 mW14-Pin CerDIP<sup>d</sup> ..... 825 mW10-Pin Metal Can<sup>e</sup> ..... 450 mW

## Notes:

- a. Signals on S<sub>X</sub>, D<sub>X</sub>, or IN<sub>X</sub> exceeding V+ or V- will be clamped by internal diodes. Limit forward diode current to maximum current ratings.
- b. All leads welded or soldered to PC Board.
- c. Derate 11 mW/°C above 75°C
- d. Derate 6.5 mW/°C above 25°C
- e. Derate 6 mW/°C above 75°C

TEMIC

Siliconix







**DG304A/305A/306A/307A****Specifications<sup>a</sup>**

Parameter	Symbol	Conditions Unless Otherwise Specified $V_+ = 15 \text{ V}$ , $V_- = -15 \text{ V}$ $V_{IN} = 3.5 \text{ V}$ or $11 \text{ V}^f$	Temp <sup>b</sup>	Typ <sup>c</sup>	A Suffix -55 to 125°C		B, C Suffix -25 to 85°C 0 to 70°C		Unit
					Min <sup>d</sup>	Max <sup>d</sup>	Min <sup>d</sup>	Max <sup>d</sup>	
<b>Analog Switch</b>									
Analog Signal Range <sup>e</sup>	$V_{ANALOG}$		Full		-15	15	-15	15	V
Drain-Source On-Resistance	$r_{DS(on)}$	$V_D = \pm 10 \text{ V}$ , $I_S = 10 \text{ mA}$	Room Full	30		50 75		50 75	$\Omega$
Source Off Leakage Current	$I_{S(off)}$	$V_S = \pm 14 \text{ V}$ $V_D = \mp 14 \text{ V}$	Room Full	$\pm 0.1$	-1 -100	1 100	-5 -100	5 100	nA
Drain Off Leakage Current	$I_{D(off)}$	$V_S = \pm 14 \text{ V}$ $V_D = \mp 14 \text{ V}$	Room Full	$\pm 0.1$	-1 -100	1 100	-5 -100	5 100	
Drain On Leakage Current	$I_{D(on)}$	$V_D = V_S = \pm 14 \text{ V}$	Room Full	$\pm 0.1$	-2 -200	2 200	-5 -200	5 200	
<b>Digital Control</b>									
Input Current with Input Voltage High	$I_{INH}$	$V_{IN} = 5 \text{ V}$	Room Full	-0.001	-1 -1		-1		$\mu\text{A}$
		$V_{IN} = 15 \text{ V}$	Room Full	0.001		1 1		1	
Input Current with Input Voltage Low	$I_{INL}$	$V_{IN} = 0 \text{ V}$	Room Full	-0.001	-1 -1		-1		
<b>Dynamic Characteristics</b>									
Turn-On Time	$t_{ON}$	See Figure 2	Room	110		250			ns
Turn-Off Time	$t_{OFF}$		Room	70		150			
Break-Before-Make Time	$t_{OPEN}$	DG305A/307A ONLY See Figure 3	Room	50					
Charge Injection	Q	$C_L = 1 \text{ nF}$ , $R_{gen} = 0$ $V_{gen} = 0 \text{ V}$ , See Figure 4	Room	30					pC
Source-Off Capacitance	$C_{S(off)}$	$f = 1 \text{ MHz}$ , $V_S = 0 \text{ V}$ $V_S, V_D = 0 \text{ V}$	Room	14					pF
Drain-Off Capacitance	$C_{D(off)}$		Room	14					
Channel-On Capacitance	$C_{D(on)}$		Room	40					
Input Capacitance	$C_{IN}$	$f = 1 \text{ MHz}$	$V_{IN} = 0 \text{ V}$	Room	6				dB
			$V_{IN} = 15 \text{ V}$	Room	7				
Off-Isolation	OIRR	$V_{IN} = 0 \text{ V}$ , $R_L = 1 \text{ k}\Omega$ $V_S = 1 \text{ V}_{rms}$ , $f = 500 \text{ kHz}$	Room	62					
Crosstalk (Channel-to-Channel)	X <sub>TALK</sub>		Room	74					
<b>Power Supplies</b>									
Positive Supply Current	I <sub>+</sub>	$V_{IN} = 15 \text{ V}$ or $0 \text{ V}$ (All Inputs)	Room Full	0.001		10 100		100	$\mu\text{A}$
Negative Supply Current	I <sub>-</sub>		Room Full	-0.001	-10 -100		-100		

Notes:

- a. Refer to PROCESS OPTION FLOWCHART (Section 5 of the 1994 Data Book or FaxBack number 7103).
- b. Room = 25°C, Full = as determined by the operating temperature suffix.
- c. Typical values are for DESIGN AID ONLY, not guaranteed nor subject to production testing.
- d. The algebraic convention whereby the most negative value is a minimum and the most positive a maximum, is used in this data sheet.
- e. Guaranteed by design, not subject to production test.
- f.  $V_{IN}$  = input voltage to perform proper function.

## Typical Characteristics




# DG304A/305A/306A/307A

**TEMIC**

**Siliconix**

## Typical Characteristics (Cont'd)



## Schematic Diagram (Typical Channel)




Figure 1.

## Test Circuits







Figure 2. Switching Time



## Test Circuits (Cont'd)



C<sub>L</sub> (includes fixture and stray capacitance)



**Figure 3.** Break-Before-Make SPDT (DG305A, DG307A)



**Figure 4.** Charge Injection

## Application Hints<sup>a</sup>

V <sub>+</sub> Positive Supply Voltage (V)	V <sub>-</sub> Negative Supply Voltage (V)	GND Voltage (V)	V <sub>IN</sub> Logic Input Voltage V <sub>INH(min)/V<sub>INL(max)</sub></sub> (V)	V <sub>S</sub> or V <sub>D</sub> Analog Voltage Range (V)
15	-15	0	11/3.5	-15 to 15
20	-20	0	11/3.5	-20 to 20
15	0	0	11/3.5	0 to 15

Notes:


a. Application Hints are for DESIGN AID ONLY, not guaranteed and not subject to production testing.

TEMIC


Siliconix

# DG304A/305A/306A/307A

## Applications



**Figure 5.** Low Power Binary to  $10^n$  Gain Low Frequency Amplifier



**Figure 6.** Low Power Non-Inverting Amplifier with Digitally Selectable Inputs and Gain