

EDISWAN

MAZDA

68508

HALF WAVE TUNGAR RECTIFIER

68508

GENERAL

Type 68508 is a Hot Gas Discharge Half-Wave Rectifier designed for use in low voltage battery charging equipment.

RATING

Filament Voltage (volts)	V_f	2.5
Filament Current (amps)	I_f	25.0
Striking Voltage (volts)	V_s	12.0
Anode to Cathode Voltage Drop (volts)		10.0
D.C. Output	60 volts	15 amps

DIMENSIONS

Maximum Overall Length (mm)	214
Maximum Overall Diameter (mm)	96
Approximate Nett Weight (ozs)	4.0
Approximate Home Packed Weight (ozs)	8.0
Approximate Export Packed Weight (ozs)	12.0

MOUNTING POSITION - Vertical

BASE - G.E.S. - Filament

TOP CONNECTION Loose Lead - Anode

68508

EDISWAN

MAZDA

68508

HALF WAVE TUNGAR RECTIFIER

