
Errata Sheet for PIC14C000 Revision A

The PIC14C000 parts you have received conform functionally to the PIC14C000 data sheet (DS40122B), except for the anomalies described below.

USING AN1 AND AN5 AS ANALOG INPUTS

1. Analog inputs AN1 and AN5 can not be used if their level-shift network is disabled. According to Section 9.2 of the PIC14C000 data sheet, (DS40122B), the level-shift network feature can be turned off by setting the LSOFF bit (SLPCON<4>). However, doing so will cause the AN1 and AN5 inputs to go to VDD, rendering them unusable as analog input channels. Therefore, the LSOFF bit must remain cleared. The other functions associated with these pins, such as the current zeroing and filtering switches, operate as specified. The AN1 and AN5 pins can still be used for ADC operations, but a small firmware routine is required to ensure accurate results. This routine can be implemented by following the steps below:
 - Ensure the LSOFF bit (SLPCON<4>) is cleared.
 - Ensure a good zero-level on AN1 and/or AN5 by setting the ADZERO bit (ADCON0<0>).
 - Perform an A/D conversion as normal and keep the count from ADCAPH and ADCAPL in user-defined RAM. This is the representative digital count for the exact level-shift value.
 - Enable the signal of interest onto AN1 and/or AN5.
 - Perform another A/D conversion and keep the count in ADCAPH and ADCAPL. This is the representative digital count for the sum of the signal of interest and the exact level-shift value.
 - Subtract the level-shift count from the representative count for the sum.
 - This result will be the representative count for the signal of interest alone.

USING THE I²C™ MODULE IN SMBus MODE

2. The I²C Module in the PIC14C000 can be used with either PORTC<7:6> or PORTD<1:0> to provide the clock and data signal connections. According to Figure 7-16 of the PIC14C000 data sheet (DS40122B), the MISC<bit 3>, SMBus bit, allows user to select the input thresholds of PORTC<7:6> and PORTD<1:0> to either be SMBus-compatible or Schmitt Trigger-compatible.

Although the data sheet says that PORTC<7:6> operates the same way as PORTD<1:0>, in the actual implementation, PORTC<7:6> always uses the Schmitt Trigger input thresholds when the I²C module reads through PORTC<7:6>, even if the SMBus mode is selected.

If PORTC<7:6> are read as port inputs, while the SMBus mode is selected, the SMBus voltage levels are used.

Interfacing to an SMBus port can still be implemented using either of the following methods:

- Use the I²C module together with PORTD<1:0>, and set the MISC<3> bit high.
- Use PORTC<7:6> or PORTD<1:0> with the MISC<3> bit set high, and perform the I²C function in firmware.

PIC14C000

Clarifications/Corrections to the Data Sheet:

In the PIC14C000 Device Data Sheet (document DS40122B), the following clarifications and corrections should be noted:

- Module: A/D
The operating current specifications during SLEEP have been modified to the values shown in Table 1.

TABLE 1: A/D CONVERTER OPERATING CURRENT DURING SLEEP MODE

Symbol	Characteristics	New Specification			Data Sheet Specification			Units	Conditions
		Min	Typ	Max	Min	Typ	Max		
IPD1	During A/D conversion: All analog on and internal oscillator active	—	500	900	—	TBD	900	μA	V _{DD} = 3.0V
IPD1		—	650	1250	—	TBD	1250	μA	V _{DD} = 4.0V

- Module: I/O Port
The Input High Voltage specification for the RC7, RC6, RD1, and RD0 in the SMBus mode has been modified to the values shown in Table 2.

TABLE 2: RC7, RC6, RD1, RD0 INPUT HIGH VOLTAGE

Symbol	Characteristics	New Specification			Data Sheet Specification			Units	Conditions
		Min	Typ	Max	Min	Typ	Max		
V _{IH}	SMBus mode (RC7, RC6, RD0, RD1)	1.4	—	6.0	1.4V	—	V _{DD}	V	SMBus bit, MISC<3> = 1

- $\overline{\text{MCLR}}$ Reset
The $\overline{\text{MCLR}}$ reset specification has been modified to the values shown in Table 3.

TABLE 3: $\overline{\text{MCLR}}$ RESET TIMING

Symbol	Characteristics	New Specification			Data Sheet Specification			Units	Conditions
		Min	Typ	Max	Min	Typ	Max		
T _{mCL}	$\overline{\text{MCLR}}$ Pulse Width (low)	2.0	—	—	0.1	—	—	μS	V _{DD} = 5V, -40°C to +85°C
T _{IOZ}	I/O High Impedance from $\overline{\text{MCLR}}$ Low	—	—	2.1	—	—	0.1	μS	

4. Module: Bandgap Voltage Reference
The condition for the Output Voltage specification has been added as shown in Table 4.

TABLE 4: BANDGAP OUTPUT VOLTAGE SPECIFICATION

Symbol	Characteristics	New Specification			Data Sheet Specification			Units	Conditions
		Min	Typ	Max	Min	Typ	Max		
VO(VREF)	Output Voltage	1.14	1.19	1.24	1.14	1.19	1.24	V	TA = 25°C

5. Module: Temperature Sensor
The Output linearity specification has been modified to the values shown in Table 5.

TABLE 5: TEMPERATURE SENSOR SPECIFICATION

Symbol	Characteristics	New Specification			Data Sheet Specification			Units	Conditions
		Min	Typ	Max	Min	Typ	Max		
LIN (temp)	Output Linearity (Note 1, 2)	—	0.5	—	—	TBD	—	°C	

Note 1: This parameter is characterized but not tested.

2: Linearity is defined as the maximum deviation over temperature from a best fit straight line.

6. Module: Internal Oscillator
The Frequency Range specification has been modified to the values shown in Table 6.

TABLE 6: INTERNAL OSCILLATOR

Symbol	Characteristics	New Specification			Data Sheet Specification			Units	Conditions
		Min	Typ	Max	Min	Typ	Max		
Fosc (in)	Frequency Range	3.0	4.0	5.5	3.0	4.0	5.0	MHz	



WORLDWIDE SALES AND SERVICE

AMERICAS

Corporate Office

Microchip Technology Inc.
2355 West Chandler Blvd.
Chandler, AZ 85224-6199
Tel: 480-786-7200 Fax: 480-786-7277
Technical Support: 480-786-7627
Web Address: <http://www.microchip.com>

Atlanta

Microchip Technology Inc.
500 Sugar Mill Road, Suite 200B
Atlanta, GA 30350
Tel: 770-640-0034 Fax: 770-640-0307

Boston

Microchip Technology Inc.
5 Mount Royal Avenue
Marlborough, MA 01752
Tel: 508-480-9990 Fax: 508-480-8575

Chicago

Microchip Technology Inc.
333 Pierce Road, Suite 180
Itasca, IL 60143
Tel: 630-285-0071 Fax: 630-285-0075

Dallas

Microchip Technology Inc.
4570 Westgrove Drive, Suite 160
Addison, TX 75248
Tel: 972-818-7423 Fax: 972-818-2924

Dayton

Microchip Technology Inc.
Two Prestige Place, Suite 150
Miamisburg, OH 45342
Tel: 937-291-1654 Fax: 937-291-9175

Detroit

Microchip Technology Inc.
Tri-Atria Office Building
32255 Northwestern Highway, Suite 190
Farmington Hills, MI 48334
Tel: 248-538-2250 Fax: 248-538-2260

Los Angeles

Microchip Technology Inc.
18201 Von Karman, Suite 1090
Irvine, CA 92612
Tel: 949-263-1888 Fax: 949-263-1338

New York

Microchip Technology Inc.
150 Motor Parkway, Suite 202
Hauppauge, NY 11788
Tel: 631-273-5305 Fax: 631-273-5335

San Jose

Microchip Technology Inc.
2107 North First Street, Suite 590
San Jose, CA 95131
Tel: 408-436-7950 Fax: 408-436-7955

AMERICAS (continued)

Toronto

Microchip Technology Inc.
5925 Airport Road, Suite 200
Mississauga, Ontario L4V 1W1, Canada
Tel: 905-405-6279 Fax: 905-405-6253

ASIA/PACIFIC

Hong Kong

Microchip Asia Pacific
Unit 2101, Tower 2
Metroplaza
223 Hing Fong Road
Kwai Fong, N.T., Hong Kong
Tel: 852-2-401-1200 Fax: 852-2-401-3431

Beijing

Microchip Technology, Beijing
Unit 915, 6 Chaoyangmen Bei Dajie
Dong Erhuan Road, Dongcheng District
New China Hong Kong Manhattan Building
Beijing 100027 PRC
Tel: 86-10-85282100 Fax: 86-10-85282104

India

Microchip Technology Inc.
India Liaison Office
No. 6, Legacy, Convent Road
Bangalore 560 025, India
Tel: 91-80-229-0061 Fax: 91-80-229-0062

Japan

Microchip Technology Intl. Inc.
Benex S-1 6F
3-18-20, Shinyokohama
Kohoku-Ku, Yokohama-shi
Kanagawa 222-0033 Japan
Tel: 81-45-471-6166 Fax: 81-45-471-6122

Korea

Microchip Technology Korea
168-1, Youngbo Bldg. 3 Floor
Samsung-Dong, Kangnam-Ku
Seoul, Korea
Tel: 82-2-554-7200 Fax: 82-2-558-5934

Shanghai

Microchip Technology
RM 406 Shanghai Golden Bridge Bldg.
2077 Yan'an Road West, Hong Qiao District
Shanghai, PRC 200335
Tel: 86-21-6275-5700 Fax: 86 21-6275-5060

ASIA/PACIFIC (continued)

Singapore

Microchip Technology Singapore Pte Ltd.
200 Middle Road
#07-02 Prime Centre
Singapore 188980
Tel: 65-334-8870 Fax: 65-334-8850

Taiwan, R.O.C

Microchip Technology Taiwan
10F-1C 207
Tung Hua North Road
Taipei, Taiwan, ROC
Tel: 886-2-2717-7175 Fax: 886-2-2545-0139

EUROPE

United Kingdom

Arizona Microchip Technology Ltd.
505 Eskdale Road
Winkers Triangle
Wokingham
Berkshire, England RG41 5TU
Tel: 44 118 921 5858 Fax: 44-118 921-5835

Denmark

Microchip Technology Denmark ApS
Regus Business Centre
Lautrup hof 1-3
Ballerup DK-2750 Denmark
Tel: 45 4420 9895 Fax: 45 4420 9910

France

Arizona Microchip Technology SARL
Parc d'Activite du Moulin de Massy
43 Rue du Saule Trapu
Batiment A - 1er Etage
91300 Massy, France
Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79

Germany

Arizona Microchip Technology GmbH
Gustav-Heinemann-Ring 125
D-81739 München, Germany
Tel: 49-89-627-144 0 Fax: 49-89-627-144-44

Italy

Arizona Microchip Technology SRL
Centro Direzionale Colleoni
Palazzo Taurus 1 V. Le Colleoni 1
20041 Agrate Brianza
Milan, Italy
Tel: 39-039-65791-1 Fax: 39-039-6899883

11/15/99



Microchip received QS-9000 quality system certification for its worldwide headquarters, design and water fabrication facilities in Chandler and Tempe, Arizona in July 1999. The Company's quality system processes and procedures are QS-9000 compliant for its PICmicro® 8-bit MCUs, KEELOC® code hopping devices, Serial EEPROMs and microperipheral products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001 certified.

All rights reserved. © 1999 Microchip Technology Incorporated. Printed in the USA. 11/99 Printed on recycled paper.

Information contained in this publication regarding device applications and the like is intended for suggestion only and may be superseded by updates. No representation or warranty is given and no liability is assumed by Microchip Technology Incorporated with respect to the accuracy or use of such information, or infringement of patents or other intellectual property rights arising from such use or otherwise. Use of Microchip's products as critical components in life support systems is not authorized except with express written approval by Microchip. No licenses are conveyed, implicitly or otherwise, under any intellectual property rights. The Microchip logo and name are registered trademarks of Microchip Technology Inc. in the U.S.A. and other countries. All rights reserved. All other trademarks mentioned herein are the property of their respective companies.