



# SQTP<sup>SM</sup> Specification for PIC16/17

---

---

## Serialized Quick Turn Programming Specification for PIC16/17

---

---

### OVERVIEW

Serialization is a method of programming PIC16/17 microcontrollers whereby each chip is programmed with a slightly different code. Typically, all locations are programmed with the same basic code except for a few contiguous bytes which are programmed with a different number (referred to as 'key' or 'ID number' or 'serial number') in each member. Typical applications of such programming are remote transmitters for car alarms or garage door openers where each unit must have a different access code.

Microchip offers a flexible SQTP program, whereby a customer can simply specify the nature of serialization. The 'serial number' generation and programming will be taken care of by the factory.

### 1.0 SERIALIZATION SCHEME SUPPORTED

#### 1.1 Locations:

The serial number must reside in contiguous locations with up to sixteen locations used. Furthermore these locations must be coded as RETLW NN, where NN= 8-bit random code, in the finished product. For details on how the RETLW instruction is typically used for serialization purposes, please see Appendix A. The customer code must be supplied without the serial code in these locations. These locations must be blank or the assembled value of a RETLW H'FF' instruction, in the customer code provided to Microchip. Microchip will insert the serial code at these locations during programming. Hex files must be in Intel hex 8-bit merged format. See Appendix B for details.

#### 1.2 Numbering Schemes:

**Random:** Truly random numbers are generated. However, there is no guarantee that the numbers will be non-repeating although the probability of such an occurrence will be infinitesimally small for a reasonably large field.

**Pseudo-Random:** Pseudo-random sequences of requested length (e.g. 32-bit long if four locations are used) starting with a 'seed value' selected by the factory. The customer may optionally specify the starting value. Pseudo-random sequences, by definition are non-repeating until all possible values are used.

**Sequential:** Sequential numbers are generated. User specifies the "starting number" and an increment value. In sequential numbering, the least significant digit is in the lowest memory location. The increment value must be between 1 and 255.

Numbers are always in hex and not in BCD or any other format.

# SQTP Specification for PIC16/17

---

## 2.0 PROGRAMMING SEQUENCE

The factory will program the “basic code” first, then program the serial number and finally program the code-protection fuse. Program memory will be verified at each stage except after code protection. Optionally, the factory may choose to program the “basic code” and the “serial number” at the same time. The customer may specify an ID number (four hex digits) to be programmed in the ID locations or elect to leave them unprogrammed.

## 3.0 SAMPLES

Three (3) verification samples will be provided. These will be programmed with factory selected random or sequential codes in the serialization locations. The three parts will be programmed with three different serial codes. If order entry has been completed, then the samples will reflect the first three codes. If code protection is requested, then one of the three samples will be code protected.

## 4.0 THE FOLLOWING LIMITATIONS APPLY TO THE SQTP PROGRAM

1. During shipment of serialized parts, no particular sequence can be guaranteed.
2. In sequential or pseudo-random numbering scheme, there may be missing serial numbers (e.g. due to QC sampling).
3. A list of serial numbers programmed can not be provided, nor will such a list be generated or maintained by Microchip.
4. For sequential and pseudo-random numbering schemes, Microchip will maintain last number used in last shipment and use the next number as the starting number for the next shipment. The customer should be prepared to provide a “new starting number” in the event the flow is disrupted due to unforeseen events.

# SQTP Specification for PIC16/17

## APPENDIX A:

Implementing a table in the program memory of PIC16C5X and PIC16C5XA:

The PIC16C5X and the PIC16C5XA family uses Harvard architecture, in which the program memory is separate from data memory. All instructions operate on data that is fetched from the register file or data memory. Since there are no instructions to read from or write to the program memory, simply storing data words in program memory is of no use. There is, however, a simple and elegant way to implement constant tables in the program memory by using the RETLW instruction. This instruction returns from a subroutine as well as loads an 8-bit constant into the W register. The following example shows how to get a byte of "serial information" from the table stored at location 000h in PIC16C54:

```
        ORG    0           ;store serial numbers
        RETLW  0FFh
        RETLW  0FFh
        RETLW  0FFh
        RETLW  0FFh
        RETLW  0FFh
        RETLW  0FFh
        RETLW  0FFh
        RETLW  0FFh
        RETLW  0FFh
        RETLW  0FFh      ;end of serial
                          ;numbers
        .
        .
main_prog ORG    XYZ       ;This is main program
        .
        .
        MOVLW byte_num     ;byte_num = 0 for 1st
                          ;byte
        CALL  get_lbyte;
        .
        .
get_lbyte MOVWF  PC        ;write W to program
                          ;counter
                          ;W = offset = 0 for
                          ;1st byte
                          ;end of get_lbyte sub
                          ;routine
        .
        .
        .
        END
```

The next example shows how a serial number may reside at location other than 000h.

```
main_prog ORG    XYZ       ;This is main program
        .
        .
        MOVLW byte_num     ;byte_num = 0 for 1st
                          ;byte
        CALL  get_lbyte;
        .
        .
get_lbyte ADDWFPC         ;W = offset
        RETLW  0ffh      ;
        RETLW  0ffh      ;
        RETLW  0ffh      ;
        RETLW  0ffh      ;
        RETLW  0ffh      ;
        RETLW  0ffh      ;
        RETLW  0ffh      ;
        RETLW  0ffh      ;end of serial
                          ;numbers
        .
        .
        END
```

## APPENDIX B:

### Standard hex file format for serial programming:

The hex file containing the 'serial numbers' will be in Intel hex 8-bit format. Since the PIC16C5X and the PIC16C5XA have 12-bit data words, all addresses are doubled in this hex format. Each line of the hex file will be for a new part. Each line can contain only up to 16 bytes (i.e. eight PIC16C5X, PIC16C5XA instruction words). The format is as follows:

:NNAAAATTHHHHHH . . . . .HHCC

where:

NN = byte count on current line (max 10h allowed)  
AAAA = address in four hex digits  
TT = record type, always 00 except 01 for EOF  
HH = Two digit hex data byte  
CC = Two digit hex checksum



## WORLDWIDE SALES AND SERVICE

### AMERICAS

#### Corporate Office

Microchip Technology Inc.  
2355 West Chandler Blvd.  
Chandler, AZ 85224-6199  
Tel: 480-786-7200 Fax: 480-786-7277  
Technical Support: 480-786-7627  
Web Address: <http://www.microchip.com>

#### Atlanta

Microchip Technology Inc.  
500 Sugar Mill Road, Suite 200B  
Atlanta, GA 30350  
Tel: 770-640-0034 Fax: 770-640-0307

#### Boston

Microchip Technology Inc.  
5 Mount Royal Avenue  
Marlborough, MA 01752  
Tel: 508-480-9990 Fax: 508-480-8575

#### Chicago

Microchip Technology Inc.  
333 Pierce Road, Suite 180  
Itasca, IL 60143  
Tel: 630-285-0071 Fax: 630-285-0075

#### Dallas

Microchip Technology Inc.  
4570 Westgrove Drive, Suite 160  
Addison, TX 75248  
Tel: 972-818-7423 Fax: 972-818-2924

#### Dayton

Microchip Technology Inc.  
Two Prestige Place, Suite 150  
Miamisburg, OH 45342  
Tel: 937-291-1654 Fax: 937-291-9175

#### Detroit

Microchip Technology Inc.  
Tri-Atria Office Building  
32255 Northwestern Highway, Suite 190  
Farmington Hills, MI 48334  
Tel: 248-538-2250 Fax: 248-538-2260

#### Los Angeles

Microchip Technology Inc.  
18201 Von Karman, Suite 1090  
Irvine, CA 92612  
Tel: 949-263-1888 Fax: 949-263-1338

#### New York

Microchip Technology Inc.  
150 Motor Parkway, Suite 202  
Hauppauge, NY 11788  
Tel: 631-273-5305 Fax: 631-273-5335

#### San Jose

Microchip Technology Inc.  
2107 North First Street, Suite 590  
San Jose, CA 95131  
Tel: 408-436-7950 Fax: 408-436-7955

### AMERICAS (continued)

#### Toronto

Microchip Technology Inc.  
5925 Airport Road, Suite 200  
Mississauga, Ontario L4V 1W1, Canada  
Tel: 905-405-6279 Fax: 905-405-6253

### ASIA/PACIFIC

#### Hong Kong

Microchip Asia Pacific  
Unit 2101, Tower 2  
Metroplaza  
223 Hing Fong Road  
Kwai Fong, N.T., Hong Kong  
Tel: 852-2-401-1200 Fax: 852-2-401-3431

#### Beijing

Microchip Technology, Beijing  
Unit 915, 6 Chaoyangmen Bei Dajie  
Dong Erhuan Road, Dongcheng District  
New China Hong Kong Manhattan Building  
Beijing 100027 PRC  
Tel: 86-10-85282100 Fax: 86-10-85282104

#### India

Microchip Technology Inc.  
India Liaison Office  
No. 6, Legacy, Convent Road  
Bangalore 560 025, India  
Tel: 91-80-229-0061 Fax: 91-80-229-0062

#### Japan

Microchip Technology Intl. Inc.  
Benex S-1 6F  
3-18-20, Shinyokohama  
Kohoku-Ku, Yokohama-shi  
Kanagawa 222-0033 Japan  
Tel: 81-45-471-6166 Fax: 81-45-471-6122

#### Korea

Microchip Technology Korea  
168-1, Youngbo Bldg. 3 Floor  
Samsung-Dong, Kangnam-Ku  
Seoul, Korea  
Tel: 82-2-554-7200 Fax: 82-2-558-5934

#### Shanghai

Microchip Technology  
RM 406 Shanghai Golden Bridge Bldg.  
2077 Yan'an Road West, Hong Qiao District  
Shanghai, PRC 200335  
Tel: 86-21-6275-5700 Fax: 86 21-6275-5060

### ASIA/PACIFIC (continued)

#### Singapore

Microchip Technology Singapore Pte Ltd.  
200 Middle Road  
#07-02 Prime Centre  
Singapore 188980  
Tel: 65-334-8870 Fax: 65-334-8850

#### Taiwan, R.O.C

Microchip Technology Taiwan  
10F-1C 207  
Tung Hua North Road  
Taipei, Taiwan, ROC  
Tel: 886-2-2717-7175 Fax: 886-2-2545-0139

### EUROPE

#### United Kingdom

Arizona Microchip Technology Ltd.  
505 Eskdale Road  
Wokingham  
Berkshire, England RG41 5TU  
Tel: 44 118 921 5858 Fax: 44-118 921-5835

#### Denmark

Microchip Technology Denmark ApS  
Regus Business Centre  
Lautrup hof 1-3  
Ballerup DK-2750 Denmark  
Tel: 45 4420 9895 Fax: 45 4420 9910

#### France

Arizona Microchip Technology SARL  
Parc d'Activite du Moulin de Massy  
43 Rue du Saule Trapu  
Batiment A - 1er Etage  
91300 Massy, France  
Tel: 33-1-69-53-63-20 Fax: 33-1-69-30-90-79

#### Germany

Arizona Microchip Technology GmbH  
Gustav-Heinemann-Ring 125  
D-81739 München, Germany  
Tel: 49-89-627-144 0 Fax: 49-89-627-144-44

#### Italy

Arizona Microchip Technology SRL  
Centro Direzionale Colleoni  
Palazzo Taurus 1 V. Le Colleoni 1  
20041 Agrate Brianza  
Milan, Italy  
Tel: 39-039-65791-1 Fax: 39-039-6899883

11/15/99



Microchip received QS-9000 quality system certification for its worldwide headquarters, design and water fabrication facilities in Chandler and Tempe, Arizona in July 1999. The Company's quality system processes and procedures are QS-9000 compliant for its PICmicro® 8-bit MCUs, KEELOC® code hopping devices, Serial EEPROMs and microperipheral products. In addition, Microchip's quality system for the design and manufacture of development systems is ISO 9001 certified.

All rights reserved. © 1999 Microchip Technology Incorporated. Printed in the USA. 11/99 Printed on recycled paper.

Information contained in this publication regarding device applications and the like is intended for suggestion only and may be superseded by updates. No representation or warranty is given and no liability is assumed by Microchip Technology Incorporated with respect to the accuracy or use of such information, or infringement of patents or other intellectual property rights arising from such use or otherwise. Use of Microchip's products as critical components in life support systems is not authorized except with express written approval by Microchip. No licenses are conveyed, implicitly or otherwise, under any intellectual property rights. The Microchip logo and name are registered trademarks of Microchip Technology Inc. in the U.S.A. and other countries. All rights reserved. All other trademarks mentioned herein are the property of their respective companies.