

Parts List DJ-496/438

Unit	Ref. No.	Parts No.	Parts Name	Version
MAIN	C1	CU3031	C1608JB1H471KT-AS	
MAIN	C2	CU3031	C1608JB1H471KT-AS	
MAIN	C3	CU3057	C1608CH1H130JT-A	
MAIN	C4	CU3014	C1608CH1H180JT-AS	
MAIN	C5	CU3031	C1608JB1H471KT-AS	496T, 496E
MAIN	C5	CU3023	C1608CH1H101JT-AS	496TA2, 438TA2
MAIN	C6	CU3031	C1608JB1H471KT-AS	
MAIN	C7	CU3007	C1608CH1H060CT-A	496T, 496E
MAIN	C7	CU3006	C1608CH1H050CT-AS	496TA2, 438TA2
MAIN	C8	CU3031	C1608JB1H471KT-AS	
MAIN	C9	CU3005	C1608CH1H040CT-AS	
MAIN	C10	CU3009	C1608CH1H080CT-A	
MAIN	C11	CU3009	C1608CH1H080CT-A	
MAIN	C12	CU3001	C1608CH1H0R5CT-AS	
MAIN	C13	CU3031	C1608JB1H471KT-AS	
MAIN	C14	CU3001	C1608CH1H0R5CT-AS	
MAIN	C15	CU3031	C1608JB1H471KT-AS	
MAIN	C16	CU3031	C1608JB1H471KT-AS	
MAIN	C17	CS0408	6MCM156MATER	
MAIN	C18	CU3007	C1608CH1H060CT-A	
MAIN	C19	CU3035	C1608JB1H102KT-AS	
MAIN	C20	CU3014	C1608CH1H180JT-AS	
MAIN	C21	CU3011	C1608CH1H100DT-AS	
MAIN	C22	NC		
MAIN	C23	CU3001	C1608CH1H0R5CT-AS	
MAIN	C24	CU3012	C1608CH1H120JT-AS	
MAIN	C25	CU3031	C1608JB1H471KT-AS	
MAIN	C26	CU3031	C1608JB1H471KT-AS	
MAIN	C27	CU3009	C1608CH1H080CT-A	
MAIN	C28	CU3001	C1608CH1H0R5CT-AS	
MAIN	C29	NC		
MAIN	C30	CU3012	C1608CH1H120JT-AS	
MAIN	C31	CU3006	C1608CH1H050CT-AS	
MAIN	C32	CU3002	C1608CH1H010CT-AS	
MAIN	C33	CU3031	C1608JB1H471KT-AS	
MAIN	C34	CU3047	C1608JB1H103KT-N	
MAIN	C35	CU3031	C1608JB1H471KT-AS	
MAIN	C36	CU3031	C1608JB1H471KT-AS	
MAIN	C37	CU3016	C1608CH1H270JT-AS	
MAIN	C38	CU3001	C1608CH1H0R5CT-AS	
MAIN	C39	NC		
MAIN	C40	CU3011	C1608CH1H100DT-AS	
MAIN	C41	CU3031	C1608JB1H471KT-AS	
MAIN	C42	CU3031	C1608JB1H471KT-AS	
MAIN	C43	CU3023	C1608CH1H101JT-AS	
MAIN	C44	CU3031	C1608JB1H471KT-AS	
MAIN	C45	CU3031	C1608JB1H471KT-AS	
MAIN	C46	CU3031	C1608JB1H471KT-AS	
MAIN	C47	CU0108	LMK212BJ105KG	
MAIN	C48	CU3031	C1608JB1H471KT-AS	
MAIN	C49	CU3013	C1608CH1H150JT-AS	
MAIN	C50	CU3031	C1608JB1H471KT-AS	
MAIN	C51	CU3031	C1608JB1H471KT-AS	
MAIN	C52	CU3031	C1608JB1H471KT-AS	
MAIN	C53	CU3031	C1608JB1H471KT-AS	
MAIN	C54	CU3047	C1608JB1H103KT-N	
MAIN	C55	CS0408	6MCM156MATER	
MAIN	C56	CU3015	C1608CH1H220JT-AS	

Parts List DJ-496/438

MAIN	C57	CU3004	C1608CH1H030CT-AS	
MAIN	C58	CU3009	C1608CH1H080CT-A	
MAIN	C59	CU3015	C1608CH1H220JT-AS	
MAIN	C60	CU3012	C1608CH1H120JT-AS	
MAIN	C61	CU3005	C1608CH1H040CT-AS	
MAIN	C62	CU3006	C1608CH1H050CT-AS	
MAIN	C63	CU3031	C1608JB1H471KT-AS	
MAIN	C64	CU3047	C1608JB1H103KT-N	
MAIN	C65	CU3004	C1608CH1H030CT-AS	
MAIN	C66	CU3004	C1608CH1H030CT-AS	
MAIN	C67	CU3006	C1608CH1H050CT-AS	
MAIN	C68	CU3023	C1608CH1H101JT-AS	
MAIN	C69	CU3047	C1608JB1H103KT-N	
MAIN	C70	CS0063	TMCSA1V104MTR	
MAIN	C71	CU3001	C1608CH1H0R5CT-AS	
MAIN	C72	CU3035	C1608JB1H102KT-AS	
MAIN	C73	CU3047	C1608JB1H103KT-N	
MAIN	C74	CU3031	C1608JB1H471KT-AS	
MAIN	C75	CU3057	C1608CH1H130JT-A	
MAIN	C76	CU3015	C1608CH1H220JT-AS	
MAIN	C77	CU3012	C1608CH1H120JT-AS	
MAIN	C78	CU3014	C1608CH1H180JT-AS	
MAIN	C79	CU3002	C1608CH1H010CT-AS	
MAIN	C80	CS0213	TMCMA1A225MTR	
MAIN	C81	CU3011	C1608CH1H100DT-AS	
MAIN	C82	CU0108	LMK212BJ105KG	
MAIN	C83	CU3031	C1608JB1H471KT-AS	
MAIN	C84	CU3031	C1608JB1H471KT-AS	
MAIN	C85	CU0108	LMK212BJ105KG	
MAIN	C86	CU3016	C1608CH1H270JT-AS	
MAIN	C87	CU3035	C1608JB1H102KT-AS	
MAIN	C88	CS0213	TMCMA1A225MTR	
MAIN	C89	CU3016	C1608CH1H270JT-AS	
MAIN	C90	CU0108	LMK212BJ105KG	
MAIN	C91	CU3035	C1608JB1H102KT-AS	
MAIN	C92	CU3035	C1608JB1H102KT-AS	
MAIN	C93	CE0392	6MV47UW	
MAIN	C94	CU3035	C1608JB1H102KT-AS	
MAIN	C95	CS0408	6MCM156MATER	
MAIN	C96	CU3035	C1608JB1H102KT-AS	
MAIN	C97	CU0108	LMK212BJ105KG	
MAIN	C98	CU3047	C1608JB1H103KT-N	
MAIN	C99	CS0408	6MCM156MATER	
MAIN	C100	CS0408	6MCM156MATER	
MAIN	C101	CU3047	C1608JB1H103KT-N	
MAIN	C102	CU3035	C1608JB1H102KT-AS	
MAIN	C103	CU0108	LMK212BJ105KG	
MAIN	C104	CU3035	C1608JB1H102KT-AS	
MAIN	C105	CS0404	6MCM106MATER	
MAIN	C106	CU3015	C1608CH1H220JT-AS	
MAIN	C107	CS0408	6MCM156MATER	
MAIN	C108	CU3035	C1608JB1H102KT-AS	
MAIN	C109	CE0350	16MV100HC	
MAIN	C110	CU3035	C1608JB1H102KT-AS	
MAIN	C111	CE0397	MVS16VC47MF46	
MAIN	C112	CU0108	LMK212BJ105KG	
MAIN	C113	CU3047	C1608JB1H103KT-N	
MAIN	C114	CU3035	C1608JB1H102KT-AS	
MAIN	C115	CE0392	6MV47UW	

Parts List DJ-496/438

MAIN	C116	CU3111	C1608JB1C104KT-N	
MAIN	C117	CU3047	C1608JB1H103KT-N	
MAIN	C118	CS0408	6MCM156MATER	
MAIN	C119	CU3047	C1608JB1H103KT-N	
MAIN	C120	CU3035	C1608JB1H102KT-AS	
MAIN	C121	CS0408	6MCM156MATER	
MAIN	C122	CU3111	C1608JB1C104KT-N	
MAIN	C123	CU3111	C1608JB1C104KT-N	
MAIN	C124	CU3035	C1608JB1H102KT-AS	
MAIN	C125	CU3051	C1608JB1E223KT-NS	
MAIN	C126	CU3051	C1608JB1E223KT-NS	
MAIN	C127	CU3051	C1608JB1E223KT-NS	
MAIN	C128	CU3111	C1608JB1C104KT-N	
MAIN	C129	CU3111	C1608JB1C104KT-N	
MAIN	C130	CU0108	LMK212BJ105KG	
MAIN	C131	CU3111	C1608JB1C104KT-N	
MAIN	C132	CE0396	MVS6.3VC100MF46	
MAIN	C133	CS0408	6MCM156MATER	
MAIN	C134	CU3111	C1608JB1C104KT-N	
MAIN	C135	CU3035	C1608JB1H102KT-AS	
MAIN	C136	CU3035	C1608JB1H102KT-AS	
MAIN	C137	CU3101	C1608JB1C473KT-NS	
MAIN	C138	CU3111	C1608JB1C104KT-N	
MAIN	C139	CU0108	LMK212BJ105KG	
MAIN	C140	CU3035	C1608JB1H102KT-AS	
MAIN	C141	CU3035	C1608JB1H102KT-AS	
MAIN	C142	CU3047	C1608JB1H103KT-N	
MAIN	C143	CU3035	C1608JB1H102KT-AS	
MAIN	C144	CU3111	C1608JB1C104KT-N	
MAIN	C145	CU3025	C1608CH1H151JT-AS	
MAIN	C146	CU3035	C1608JB1H102KT-AS	
MAIN	C147	CU3035	C1608JB1H102KT-AS	
MAIN	C148	CU3111	C1608JB1C104KT-N	
MAIN	C149	CU3041	C1608JB1H332KT-NS	
MAIN	C150	CU3111	C1608JB1C104KT-N	
MAIN	C151	CU3111	C1608JB1C104KT-N	
MAIN	C152	CU3035	C1608JB1H102KT-AS	
MAIN	C153	CU3035	C1608JB1H102KT-AS	
MAIN	C154	CU3038	C1608JB1H182KT-AS	
MAIN	C155	CU3111	C1608JB1C104KT-N	
MAIN	C156	CU3035	C1608JB1H102KT-AS	
MAIN	C157	CU3050	C1608JB1E183KT-NS	
MAIN	C158	CU0108	LMK212BJ105KG	
MAIN	C159	CU3051	C1608JB1E223KT-NS	
MAIN	C160	CU0108	LMK212BJ105KG	
MAIN	C161	CS0408	6MCM156MATER	
MAIN	C162	CU3023	C1608CH1H101JT-AS	
MAIN	C163	CU3044	C1608JB1H562KT-NS	
MAIN	C164	CU3040	C1608JB1H272KT-NS	
MAIN	C165	CU3111	C1608JB1C104KT-N	
MAIN	C166	CU3047	C1608JB1H103KT-N	
MAIN	C167	CU3101	C1608JB1C473KT-NS	
MAIN	C168	CU3047	C1608JB1H103KT-N	
MAIN	C169	CU3047	C1608JB1H103KT-N	
MAIN	C170	CU3043	C1608JB1H472KT-NS	
MAIN	C171	CU3043	C1608JB1H472KT-NS	
MAIN	C172	CU3035	C1608JB1H102KT-AS	
MAIN	C173	CU0108	LMK212BJ105KG	
MAIN	C174	CS0408	6MCM156MATER	

Parts List DJ-496/438

MAIN	C175	CU3111	C1608JB1C104KT-N	
MAIN	C176	CU3014	C1608CH1H180JT-AS	
MAIN	C177	CU3013	C1608CH1H150JT-AS	
MAIN	C178	CU0108	LMK212BJ105KG	
MAIN	C179	CU3035	C1608JB1H102KT-AS	
MAIN	C180	CU3111	C1608JB1C104KT-N	
MAIN	C181	CU3049	C1608JB1E153KT-NS	
MAIN	C182	CU3031	C1608JB1H471KT-AS	
MAIN	C183	CU3031	C1608JB1H471KT-AS	
MAIN	C184	NC		
MAIN	C185	CU3111	C1608JB1C104KT-N	
MAIN	C186	CU3003	C1608CH1H020CT-AS	
MAIN	C187	CU3111	C1608JB1C104KT-N	
MAIN	C188	CS0398	TMCP0J225MTR	
MAIN	C189	NC		
MAIN	C190	CU3111	C1608JB1C104KT-N	
MAIN	C191	NC		
MAIN	C251	NC		
MAIN	C301	NC		
MAIN	C302	NC		
MAIN	C303	NC		
MAIN	CN1	NC		
MAIN	CN2	UE0369	AXN49301616	
MAIN	CN3	NC		
MAIN	D1	XD0323	MA2S111-TX	
MAIN	D2	XD0326	1SV307(TPH3)	
MAIN	D3	XD0344	1SV311 (TPL3)	
MAIN	D4	XD0331	HSU277TRF	
MAIN	D5	XD0331	HSU277TRF	
MAIN	D7	XD0251	MA741WA TX	
MAIN	D8	XD0261	S3DG7	
MAIN	D9	XD0323	MA2S111-TX	
MAIN	D10	XD0130	DA204U T106	
MAIN	D11	XD0294	U2FWJ44N(TE12R)	
MAIN	D12	XD0344	1SV311 (TPL3)	
MAIN	D13	XD0344	1SV311 (TPL3)	
MAIN	D14	XD0344	1SV311 (TPL3)	
MAIN	D15	XD0344	1SV311 (TPL3)	
MAIN	D16	XD0131	1SV214 TPH4	
MAIN	D17	XL0036	SML-310MTT86	
MAIN	D18	XL0036	SML-310MTT86	
MAIN	D19	XL0028	BRPG1201W TR	
MAIN	D20	XL0036	SML-310MTT86	
MAIN	D21	XL0036	SML-310MTT86	
MAIN	D22	XL0036	SML-310MTT86	
MAIN	D23	XL0036	SML-310MTT86	
MAIN	D24	NC		
MAIN	D25	XD0332	RB706F-40-T106	
MAIN	D26	XD0291	MA729-TX	
MAIN	D27	XD0342	1SS390 TE61	
MAIN	D301	NC		
MAIN	FL1	XC0072	ALFCM455F=K	
MAIN	IC1	XA0968	uPC2710TB	
MAIN	IC2	XA0915	M64076AGP	
MAIN	IC3	XA0888	XC6202P502PR	
MAIN	IC4	XA0515	TK14521MTL	
MAIN	IC5	XA0210	NJM2070M T1	
MAIN	IC6	XA0385	M5222FP-600C	
MAIN	IC7	XA0596	NJM2902V-TE1	

Parts List DJ-496/438

MAIN	IC8	XA0573	NJM2904V-TE1	
MAIN	IC9	XA0725	M38267M8L252GP	
MAIN	IC10	XA0368	AT24C16N-10SI-2.7TER	
MAIN	IC11	XA0620	S80845CLMC-B66-T2	
MAIN	JK1	UJ0046	MJ82-1	
MAIN	JK2	UJ0019	HSJ1493-01-010	
MAIN	JK3	UJ0022	HSJ1102-01-540	
MAIN	L1	QC0507	LK16081R0K-T	
MAIN	L2	QKA45A	MR1.5 4.5T 0.4	
MAIN	L3	QKA45A	MR1.5 4.5T 0.4	
MAIN	L4	QC0507	LK16081R0K-T	
MAIN	L5	QKA25A	MR1.5 2.5T 0.4	
MAIN	L6	QKA25A	MR1.5 2.5T 0.4	
MAIN	L7	QC0558	LL1608-FH5N6S	
MAIN	L8	QC0529	LQN21A18NJ04	
MAIN	L9	QKA75A	MR1.5 7.5T 0.4	
MAIN	L10	QC0573	LL1608-FHR10J	
MAIN	L11	QC0565	LL1608-FH22NJ	
MAIN	L12	QS40124	0.40-1.20-4T-L	496T, 496E
MAIN	L12	QS401154	0.40-1.15-4T-R	496TA2, 438TA2
MAIN	L13	QC0567	LL1608-FH33NJ	
MAIN	L14	QC0561	LL1608-FH10NJ	
MAIN	L15	QC0507	LK16081R0K-T	
MAIN	L18	QC0507	LK16081R0K-T	
MAIN	L19	QC0561	LL1608-FH10NJ	
MAIN	L20	QC0528	LQN21A15NJ04	
MAIN	L21	QC0528	LQN21A15NJ04	
MAIN	L22	QC0564	LL1608-FH18NJ	
MAIN	L23	QC0562	LL1608-FH12NJ	
MAIN	L24	QC0569	LL1608-FH47NJ	
MAIN	L25	QC0534	LQN21A47NJ04	
MAIN	L26	QC0089	NL322522T-181JA	
MAIN	L27	QC0507	LK16081R0K-T	
MAIN	LCD1	EL0044	HT-3404	
MAIN	MIC1	EY0017	OB-27P44	
MAIN	Q1	XT0135	2SD2216R-TX	
MAIN	Q2	XE0038	2SK2975-T11-A	
MAIN	Q3	XT0138	2SC5066-O(TE85L)	
MAIN	Q4	XE0044	2SK3074 TE12L	
MAIN	Q5	XT0138	2SC5066-O(TE85L)	
MAIN	Q6	XU0172	XP1501-TX	
MAIN	Q7	XT0170	2SB766A-TX	
MAIN	Q8	XT0172	2SC4618TLP	
MAIN	Q9	XT0138	2SC5066-O(TE85L)	
MAIN	Q10	XT0171	2SC4808-TX.AR	
MAIN	Q11	XT0171	2SC4808-TX.AR	
MAIN	Q12	XU0193	RN1107 TE85L	
MAIN	Q13	XT0170	2SB766A-TX	
MAIN	Q14	XT0170	2SB766A-TX	
MAIN	Q15	XU0193	RN1107 TE85L	
MAIN	Q16	XU0172	XP1501-TX	
MAIN	Q17	XT0110	2SA1036K T146Q	
MAIN	Q18	XU0193	RN1107 TE85L	
MAIN	Q19	XU0197	RN1111 (TE85L)	
MAIN	Q20	XU0172	XP1501-TX	
MAIN	Q21	XU0161	XP1114(TX)	
MAIN	Q22	XU0192	RN2107 TE85L	
MAIN	Q23	XT0135	2SD2216R-TX	
MAIN	Q24	XU0197	RN1111 (TE85L)	

Parts List DJ-496/438

MAIN	Q25	XU0197	RN1111 (TE85L)	
MAIN	Q26	XU0193	RN1107 TE85L	
MAIN	Q27	XT0095	2SC4081 T106R	
MAIN	Q28	XU0192	RN2107 TE85L	
MAIN	Q29	XU0092	UN911H-TX	
MAIN	Q30	XU0195	RN1104 TE85L	
MAIN	Q31	XT0135	2SD2216R-TX	
MAIN	Q32	XE0029	2SK1580-T1	
MAIN	Q33	XT0135	2SD2216R-TX	
MAIN	Q34	XE0029	2SK1580-T1	
MAIN	Q35	XU0194	RN2111 TE85L	
MAIN	Q36	XU0197	RN1111 (TE85L)	
MAIN	Q37	XT0171	2SC4808-TX.AR	
MAIN	R1	RK3030	MCR03EZJ221	
MAIN	R2	RK3034	MCR03EZJ471	
MAIN	R3	RK3046	MCR03EZJ472	
MAIN	R4	RK3050	MCR03EZJ103	
MAIN	R5	RK3030	MCR03EZJ221	
MAIN	R6	RK3066	MCR03EZJ224	
MAIN	R7	RK3014	MCR03EZJ100	
MAIN	R8	RK3048	MCR03EZJ682	
MAIN	R9	RK3026	MCR03EZJ101	
MAIN	R10	RK3018	MCR03EZJ220	
MAIN	R11	RK3050	MCR03EZJ103	
MAIN	R12	RK3063	MCR03EZJ124	
MAIN	R13	RK3034	MCR03EZJ471	
MAIN	R14	RK3026	MCR03EZJ101	
MAIN	R16	RK3062	MCR03EZJ104	
MAIN	R18	RK3050	MCR03EZJ103	
MAIN	R19	RK3058	MCR03EZJ473	
MAIN	R20	RK3062	MCR03EZJ104	
MAIN	R21	RK3056	MCR03EZJ333	
MAIN	R22	RK3074	MCR03EZJ105	
MAIN	R23	RK3052	MCR03EZJ153	
MAIN	R24	RK3058	MCR03EZJ473	
MAIN	R25	RK0002	ERJ6GEYJ120V	
MAIN	R26	RK3050	MCR03EZJ103	
MAIN	R27	RK3034	MCR03EZJ471	
MAIN	R28	RK3042	MCR03EZJ222	
MAIN	R29	RK3050	MCR03EZJ103	
MAIN	R30	NC		
MAIN	R31	RK3026	MCR03EZJ101	
MAIN	R33	RK3050	MCR03EZJ103	
MAIN	R34	RK3062	MCR03EZJ104	
MAIN	R35	RK3034	MCR03EZJ471	
MAIN	R36	RK3066	MCR03EZJ224	
MAIN	R37	RK3050	MCR03EZJ103	
MAIN	R38	RK3046	MCR03EZJ472	
MAIN	R39	RK3062	MCR03EZJ104	
MAIN	R40	RK3063	MCR03EZJ124	
MAIN	R41	RK3035	MCR03EZJ561	
MAIN	R42	RK3038	MCR03EZJ102	
MAIN	R43	RK3050	MCR03EZJ103	
MAIN	R44	RK3048	MCR03EZJ682	
MAIN	R45	RK3050	MCR03EZJ103	
MAIN	R46	RK3032	MCR03EZJ331	
MAIN	R47	RK3030	MCR03EZJ221	
MAIN	R48	RK3050	MCR03EZJ103	
MAIN	R49	RK3058	MCR03EZJ473	

Parts List DJ-496/438

MAIN	R50	RK3038	MCR03EZHJ102	
MAIN	R51	RK3026	MCR03EZHJ101	
MAIN	R52	RK3074	MCR03EZHJ105	
MAIN	R53	RK3074	MCR03EZHJ105	
MAIN	R54	RK3074	MCR03EZHJ105	
MAIN	R55	RK3074	MCR03EZHJ105	
MAIN	R57	RK3030	MCR03EZHJ221	
MAIN	R58	RK3074	MCR03EZHJ105	
MAIN	R59	RK3066	MCR03EZHJ224	
MAIN	R60	RK3064	MCR03EZHJ154	
MAIN	R61	RK3050	MCR03EZHJ103	
MAIN	R62	RK3058	MCR03EZHJ473	
MAIN	R63	RK3062	MCR03EZHJ104	
MAIN	R64	RK3050	MCR03EZHJ103	
MAIN	R65	RK3058	MCR03EZHJ473	
MAIN	R66	RK3054	MCR03EZHJ223	
MAIN	R67	RK3076	MCR03EZHJ155	
MAIN	R68	RK3076	MCR03EZHJ155	
MAIN	R69	RK3058	MCR03EZHJ473	
MAIN	R70	RK3054	MCR03EZHJ223	
MAIN	R71	RK3042	MCR03EZHJ222	
MAIN	R72	RK3058	MCR03EZHJ473	
MAIN	R73	RK3036	MCR03EZHJ681	
MAIN	R74	RK3050	MCR03EZHJ103	
MAIN	R75	RK3058	MCR03EZHJ473	
MAIN	R76	RK3054	MCR03EZHJ223	
MAIN	R77	RK3050	MCR03EZHJ103	
MAIN	R78	RK3054	MCR03EZHJ223	
MAIN	R79	RK3022	MCR03EZHJ470	
MAIN	R80	RK3062	MCR03EZHJ104	
MAIN	R81	RK3042	MCR03EZHJ222	
MAIN	R82	RK3046	MCR03EZHJ472	
MAIN	R83	RK3050	MCR03EZHJ103	
MAIN	R84	RK3036	MCR03EZHJ681	
MAIN	R85	RK3050	MCR03EZHJ103	
MAIN	R86	RK3038	MCR03EZHJ102	
MAIN	R87	RK3050	MCR03EZHJ103	
MAIN	R88	NC		
MAIN	R89	RK3001	MCR03EZHJ000	
MAIN	R90	RK3032	MCR03EZHJ331	
MAIN	R91	RK3062	MCR03EZHJ104	
MAIN	R92	RK3058	MCR03EZHJ473	
MAIN	R93	RK3050	MCR03EZHJ103	
MAIN	R94	RK3050	MCR03EZHJ103	
MAIN	R95	RK3036	MCR03EZHJ681	
MAIN	R96	RK3032	MCR03EZHJ331	
MAIN	R97	RK3058	MCR03EZHJ473	
MAIN	R98	RK3044	MCR03EZHJ332	
MAIN	R99	RK3050	MCR03EZHJ103	
MAIN	R100	NC		
MAIN	R101	RK3036	MCR03EZHJ681	
MAIN	R102	RK3062	MCR03EZHJ104	
MAIN	R103	RK3050	MCR03EZHJ103	
MAIN	R104	RK3050	MCR03EZHJ103	
MAIN	R105	RK3041	MCR03EZHJ182	
MAIN	R106	RK3052	MCR03EZHJ153	
MAIN	R107	RK3048	MCR03EZHJ682	
MAIN	R108	RK3052	MCR03EZHJ153	
MAIN	R109	RK3050	MCR03EZHJ103	

Parts List DJ-496/438

MAIN	R110	RK3050	MCR03EZHZ103	
MAIN	R111	RK3066	MCR03EZHZ224	
MAIN	R112	RK3054	MCR03EZHZ223	
MAIN	R113	RK3050	MCR03EZHZ103	
MAIN	R114	RK3038	MCR03EZHZ102	
MAIN	R115	RK3062	MCR03EZHZ104	
MAIN	R116	RK3066	MCR03EZHZ224	
MAIN	R117	RK3074	MCR03EZHZ105	
MAIN	R118	RK3014	MCR03EZHZ100	
MAIN	R119	RK3051	MCR03EZHZ123	
MAIN	R120	RK3042	MCR03EZHZ222	
MAIN	R121	NC		
MAIN	R122	RK3032	MCR03EZHZ331	
MAIN	R123	RK3062	MCR03EZHZ104	
MAIN	R124	RK3070	MCR03EZHZ474	
MAIN	R125	RK1018	ERJ8GEYJ101V	
MAIN	R126	RK3058	MCR03EZHZ473	
MAIN	R127	RK3062	MCR03EZHZ104	
MAIN	R128	RK3062	MCR03EZHZ104	
MAIN	R129	RK3055	MCR03EZHZ273	
MAIN	R130	RK3062	MCR03EZHZ104	
MAIN	R131	RK3055	MCR03EZHZ273	
MAIN	R132	RK3046	MCR03EZHZ472	
MAIN	R133	RK3046	MCR03EZHZ472	
MAIN	R134	RK3046	MCR03EZHZ472	
MAIN	R135	RK3046	MCR03EZHZ472	
MAIN	R136	RK3074	MCR03EZHZ105	
MAIN	R137	RK3046	MCR03EZHZ472	
MAIN	R138	RK3022	MCR03EZHZ470	
MAIN	R139	RK3057	MCR03EZHZ393	
MAIN	R140	RK3058	MCR03EZHZ473	
MAIN	R141	RK3054	MCR03EZHZ223	
MAIN	R142	RK3042	MCR03EZHZ222	
MAIN	R143	RK3058	MCR03EZHZ473	
MAIN	R144	RK3061	MCR03EZHZ823	
MAIN	R145	RK3050	MCR03EZHZ103	
MAIN	R146	RK3058	MCR03EZHZ473	
MAIN	R147	RK3045	MCR03EZHZ392	
MAIN	R148	RK3063	MCR03EZHZ124	
MAIN	R149	RK3040	MCR03EZHZ152	
MAIN	R150	RK3038	MCR03EZHZ102	
MAIN	R151	RK3038	MCR03EZHZ102	
MAIN	R152	RK3062	MCR03EZHZ104	
MAIN	R153	RK3065	MCR03EZHZ184	
MAIN	R154	RK3061	MCR03EZHZ823	
MAIN	R155	RK3057	MCR03EZHZ393	
MAIN	R156	RK3049	MCR03EZHZ822	
MAIN	R157	RK3059	MCR03EZHZ563	
MAIN	R158	RK3063	MCR03EZHZ124	
MAIN	R159	RK3052	MCR03EZHZ153	
MAIN	R160	RK3068	MCR03EZHZ334	
MAIN	R161	RK3045	MCR03EZHZ392	
MAIN	R162	RK3062	MCR03EZHZ104	
MAIN	R163	RK3048	MCR03EZHZ682	
MAIN	R164	RK3038	MCR03EZHZ102	
MAIN	R165	RK3050	MCR03EZHZ103	
MAIN	R166	RK3074	MCR03EZHZ105	
MAIN	R167	RK3038	MCR03EZHZ102	
MAIN	R168	RK3046	MCR03EZHZ472	

Parts List DJ-496/438

MAIN	R169	RK3066	MCR03EZHJ224	
MAIN	R170	RK3069	MCR03EZHJ394	
MAIN	R171	RK3072	MCR03EZHJ684	
MAIN	R172	RK3050	MCR03EZHJ103	
MAIN	R173	RK3050	MCR03EZHJ103	
MAIN	R174	RK3050	MCR03EZHJ103	
MAIN	R175	RK3038	MCR03EZHJ102	
MAIN	R176	RK3060	MCR03EZHJ683	
MAIN	R177	RK3067	MCR03EZHJ274	
MAIN	R178	RK3050	MCR03EZHJ103	
MAIN	R179	RK3061	MCR03EZHJ823	
MAIN	R180	RK3055	MCR03EZHJ273	
MAIN	R181	RK3062	MCR03EZHJ104	
MAIN	R182	RK3050	MCR03EZHJ103	
MAIN	R183	RK3051	MCR03EZHJ123	
MAIN	R184	RK3063	MCR03EZHJ124	
MAIN	R185	RK3048	MCR03EZHJ682	
MAIN	R186	RK3038	MCR03EZHJ102	
MAIN	R187	RK3046	MCR03EZHJ472	
MAIN	R188	RK3038	MCR03EZHJ102	
MAIN	R189	RK3046	MCR03EZHJ472	
MAIN	R190	RK3050	MCR03EZHJ103	
MAIN	R191	RK3050	MCR03EZHJ103	
MAIN	R192	RK3066	MCR03EZHJ224	
MAIN	R193	RK3066	MCR03EZHJ224	
MAIN	R194	RK3074	MCR03EZHJ105	
MAIN	R195	NC		
MAIN	R196	RK3062	MCR03EZHJ104	
MAIN	R197	RK3062	MCR03EZHJ104	
MAIN	R198	RK3001	MCR03EZHJ000	
MAIN	R199	RK3066	MCR03EZHJ224	
MAIN	R200	RK3066	MCR03EZHJ224	
MAIN	R201	RK3074	MCR03EZHJ105	
MAIN	R202	RK3062	MCR03EZHJ104	
MAIN	R203	RK3062	MCR03EZHJ104	
MAIN	R204	RK3062	MCR03EZHJ104	
MAIN	R205	RK3066	MCR03EZHJ224	
MAIN	R206	RK3074	MCR03EZHJ105	
MAIN	R207	RK3074	MCR03EZHJ105	
MAIN	R208	RK3058	MCR03EZHJ473	
MAIN	R209	RK3038	MCR03EZHJ102	
MAIN	R210	NC		
MAIN	R211	RK3054	MCR03EZHJ223	496E
MAIN	R212	NC		
MAIN	R213	NC		
MAIN	R214	RK3046	MCR03EZHJ472	
MAIN	R215	NC		
MAIN	R216	RK3062	MCR03EZHJ104	
MAIN	R217	RK3043	MCR03EZHJ272	
MAIN	R218	RK0107	ERJ6GEY0R00V	
MAIN	R219	RK3063	MCR03EZHJ124	
MAIN	R220	RK3066	MCR03EZHJ224	
MAIN	R221	RK3030	MCR03EZHJ221	
MAIN	R222	RK3030	MCR03EZHJ221	
MAIN	R223	NC		
MAIN	R224	RK3062	MCR03EZHJ104	
MAIN	R225	NC		
MAIN	R226	RK3001	MCR03EZHJ000	
MAIN	R227	RK3040	MCR03EZHJ152	496T, 496E

Parts List DJ-496/438

MAIN	R227	RK3042	MCR03EZHZ222	496TA2, 438TA2
MAIN	R228	NC		
MAIN	R229	RK3062	MCR03EZHZ104	
MAIN	R230	RK3050	MCR03EZHZ103	
MAIN	R231	RK3062	MCR03EZHZ104	
MAIN	R232	RK3050	MCR03EZHZ103	
MAIN	R234	RK3001	MCR03EZHZ000	
MAIN	R235	NC		
MAIN	R236	NC		
MAIN	R237	RK3001	MCR03EZHZ000	
MAIN	R238	NC		
MAIN	R239	NC		
MAIN	R240	NC		
MAIN	R241	NC		
MAIN	R301	NC		
MAIN	SW17	UU0030	EVQPJ005Q	
MAIN	SW18	UU0030	EVQPJ005Q	
MAIN	TC1	CT0046	TC03C100A-TP02	
MAIN	VR1	RH0140	MVR22HXBRN472	
MAIN	VR2	RH0146	MVR22HXBRN473	
MAIN	VR3	RH0140	MVR22HXBRN472	
MAIN	VR301	NC		
MAIN	W3	MACLH2GG	#30AH1-025-H1	
MAIN	X1	XQ0112	UM-5 21.250MHZ	
MAIN	X2	XQ0122	XA10818 UM5 45.555M	
MAIN	X3	XQ0131	CSA310 3.686400MHZ	
MAIN	X301	NC		
MAIN	XF1	XF0037	MCF 45N15B5	
MAIN		UP0480A	DJ496 INTEGRATED-3	
Mechanical Parts	RE1	UR0019	RH70N00E20 (RY-6320)	
Mechanical Parts	W1	MACL07AA	#30A02-070-02	
Mechanical Parts	W2	MPCL07AA	#30P02-070-02	
Mechanical Parts		AF0012	0PH M2+ FE/ZN3	
Mechanical Parts		AF0020Z	1P 2X3 NIC	
Mechanical Parts		AF0029	XQN2+C9FN	
Mechanical Parts		AK0001Z	BT 3P 2X4 NIC	
Mechanical Parts		AN0012	RND N7X0.75 BR/B.ZN	
Mechanical Parts		DG0035	LCD LIGHT	
Mechanical Parts		DP0130	LCD PANEL DJ496	496T, 496E, 496TA2
Mechanical Parts		DP0140	LCD PANEL DJ438	438TA2
Mechanical Parts		ES0024	36-8BB-21	
Mechanical Parts		FF0029	CLOTH 4.0X22	
Mechanical Parts		FG0274	DC CAP	
Mechanical Parts		FG0286	KL6766-JACK CAPDJ195	
Mechanical Parts		FG0289	TERMINAL RUBBER 195	
Mechanical Parts		FG0290	KL6767-PTT DJ195	
Mechanical Parts		FG0291	LCD RUBBER CONNECT.	
Mechanical Parts		FG0304	KL3735-3 16KEY DJ196	
Mechanical Parts		FG0324	LCD CUSHION DJ496	
Mechanical Parts		FM0176	PLUS TERMINAL DJ195	
Mechanical Parts		FM0178	PIN DJ195	
Mechanical Parts		FM0179	ANTENNA EARTH DJ195	
Mechanical Parts		FM0187	REAR PANEL DJ196	
Mechanical Parts		FM0213	RADIATIVE PLATE 296	
Mechanical Parts		KZ0098	FRONT CASE DJ195	
Mechanical Parts		NK0068	DIAL KNOB DJ195	
Mechanical Parts		RD0108	J1/6Z	
Mechanical Parts		SS0092A	CHASSIS DJ196	
Mechanical Parts		ST0063	LCD HOLDER DJ195	

Parts List DJ-496/438

Mechanical Parts		TL0022	REFLECTIVE SHEET 195	
Mechanical Parts		TS0142	VCO CASE XH655	
Mechanical Parts		TS0148	VCO SHIELD DJP85	
Mechanical Parts		TW0020	W.PROOF A XH720	
Mechanical Parts		TZ0049	SILICON DUMPER	
Mechanical Parts		UE0441	S12-29-2-50 OHM	
Mechanical Parts		YX0024	LCD TAPE DJ195	