

BER/BLER Measurement Solution for W-CDMA Receive Module

- MU860x20A Demodulation Unit
- MX860x20A W-CDMA BER/BLER Measurement Software


(Both incorporated in MS860xA Transmitter Tester)

BER/BLER measurement achieved at receive module level!!

Features

- Optimum for the evaluation of Direct Conversion IC!!
- BER measurement is performable with/without decoding (Viterbi, Turbo).
(BLER measurement is performable only with decoding)
- Demodulated data for log acquisition (Data, Clock, Enable, Error) and I/Q level data for module output control (12bit, Serial) are outputted from the rear.

Connection image



Required system


*Refer to individual catalogs for detailed configurations.

- **MS860xA Transmitter Tester (with MU860x20A/MX860x20A incorporated)**
MX860x01B W-CDMA Measurement Software (recommended)
- **MG3681A Digital Modulation Signal Generator**
MU368040A CDMA Modulation Unit
MX368041A W-CDMA Software
MU368060A AWGN Unit (recommended)

Main specifications

- Balanced input : Differential voltage: 0.1 to 1.0Vp-p (input terminal)
 In-phase voltage : $\pm 2.5V$ (input terminal)
- Unbalanced input : 0.1 to 1.0Vp-p (input terminal)
 DC/AC switchable
- BER measurement
 Bit count : 1000 to 100M, 1 Step
 PN type : PN9/15 selectable
 Result display : Error bit count/Error rate (exponent, %) display selectable
- BLER measurement
 Block count : 10 to 100000, 1 Step
 Result display : Error block count/Error rate (exponent, %) display selectable
 Setup parameter : Parameter file for 12.2kbps/64kbps/144kbps/384kbps selectable

Measurement result example (typical value)



Specifications are subject to change without notice.

ANRITSU CORPORATION

1800 Onna, Atsugi-shi, Kanagawa, 243-8555 Japan
 Phone: +81-046-223-1111
 Fax: +81-46-296-1264

• U.S.A.

ANRITSU COMPANY

North American Region Headquarters
 1155 East Collins Blvd., Richardson, TX 75081, U.S.A.
 Toll Free: 1-800-ANRITSU (267-4878)
 Phone: +1-972-644-1777
 Fax: +1-972-671-1877

• Canada

ANRITSU ELECTRONICS LTD.
 700 Silver Seven Road, Suite 120, Kanata,
 ON K2V 1C3, Canada
 Phone: +1-613-591-2003
 Fax: +1-613-591-1006

• Brasil

ANRITSU ELETRÔNICA LTDA.
 Praça Amadeu Amaral, 27 - 1 andar
 01327-010 - Paraisópolis, São Paulo, Brazil
 Phone: +55-11-2283-2511
 Fax: +55-21-2986940

• U.K.

ANRITSU LTD.
 200 Capability Green, Luton, Bedfordshire LU1 3LU, U.K.
 Phone: +44-1582-433280
 Fax: +44-1582-731303

• Germany

ANRITSU GmbH
 Grafenberger Allee 54-56, 40237 Düsseldorf, Germany
 Phone: +49-211-96855-0
 Fax: +49-211-96855-55

• France

ANRITSU S.A.
 9, Avenue du Québec Z.A. de Courtabœuf 91951 Les
 Ulis Cedex, France
 Phone: +33-1-60-92-15-50
 Fax: +33-1-64-46-10-65

• Italy

ANRITSU S.p.A.
 Via Elio Vittorini, 129, 00144 Roma EUR, Italy
 Phone: +39-06-509-9711
 Fax: +39-06-502-24-25

• Sweden

ANRITSU AB
 Botvid Center, Fittja Backe 1-3 145 84 Stockholm,
 Sweden
 Phone: +46-853470700
 Fax: +46-853470730

• Singapore

ANRITSU PTE LTD.
 10, Hoe Chiang Road #07-01/02, Keppel Towers,
 Singapore 089315
 Phone: +65-6282-2400
 Fax: +65-6282-2533

• Hong Kong

ANRITSU COMPANY LTD.
 Suite 923, 9/F., Chinachem Golden Plaza, 77 Mody
 Road, Tsimshatsui East, Kowloon, Hong Kong, China
 Phone: +852-2301-4980
 Fax: +852-2301-3545

• P. R. China

ANRITSU COMPANY LTD.
Beijing Representative Office
 Room 1515, Beijing Fortune Building, No. 5 North
 Road, the East 3rd Ring Road, Chao-Yang District
 Beijing 100004, P.R. China
 Phone: +86-10-6590-9230

• Korea

ANRITSU CORPORATION
 8F Hyun Juk Bldg. 832-41, Yeoksam-dong,
 Kangnam-ku, Seoul, 135-080, Korea
 Phone: +82-2-553-6603
 Fax: +82-2-553-6604-5

• Australia

ANRITSU PTY LTD.
 Unit 3/170 Forster Road Mt. Waverley, Victoria, 3149,
 Australia
 Phone: +61-3-9558-8177
 Fax: +61-3-9558-8255

• Taiwan

ANRITSU COMPANY INC.
 7F, No. 316, Sec. 1, NeiHu Rd., Taipei, Taiwan
 Phone: +886-2-8751-1816
 Fax: +886-2-8751-1817

030508