

91-21-11

WIRE LIST

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-----------------|-----------|-------------|-------------|------|-------------|-------------|------|-------------|
| EFFECTIVE PAGES | | | W0000 cont. | | | W0060 cont. | | |
| | 1 thru 21 | Oct 09/2008 | O | 26 | Oct 09/2008 | O | 8 | Oct 09/2008 |
| | 22 | BLANK | R | 27 | Oct 09/2008 | R | 9 | Oct 09/2008 |
| W0000 | 1 | Jan 21/2005 | O | 28 | Oct 09/2008 | O | 10 | Oct 09/2008 |
| | 2 | Jan 21/2005 | R | 29 | Oct 09/2008 | O | 11 | Oct 09/2008 |
| | 3 | Jan 21/2005 | R | 30 | Oct 09/2008 | R | 12 | Oct 09/2008 |
| | 4 | Jan 21/2005 | R | 31 | Oct 09/2008 | O | 13 | Oct 09/2008 |
| R | 5 | Oct 09/2008 | O | 32 | Oct 09/2008 | O | 14 | Oct 09/2008 |
| O | 6 | Oct 09/2008 | O | 33 | Oct 09/2008 | O | 15 | Oct 09/2008 |
| O | 7 | Oct 09/2008 | O | 34 | Oct 09/2008 | O W0070 | 1 | Oct 09/2008 |
| O | 8 | Oct 09/2008 | O | 35 | Oct 09/2008 | R | 2 | Oct 09/2008 |
| R | 9 | Oct 09/2008 | A | 36 | Oct 09/2008 | R | 3 | Oct 09/2008 |
| O | 10 | Oct 09/2008 | O W0010 | 1 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| R | 11 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| O | 12 | Oct 09/2008 | R | 3 | Oct 09/2008 | O W0100 | 1 | Oct 09/2008 |
| O | 13 | Oct 09/2008 | R | 4 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 14 | Oct 09/2008 | A | 5 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 15 | Oct 09/2008 | R W0030 | 1 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| O | 16 | Oct 09/2008 | R | 2 | Oct 09/2008 | O W0110 | 1 | Oct 09/2008 |
| O | 17 | Oct 09/2008 | A | 3 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 18 | Oct 09/2008 | O W0040 | 1 | Oct 09/2008 | R | 3 | Oct 09/2008 |
| O | 19 | Oct 09/2008 | R W0060 | 1 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| O | 20 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| O | 21 | Oct 09/2008 | O | 3 | Oct 09/2008 | R | 6 | Oct 09/2008 |
| O | 22 | Oct 09/2008 | O | 4 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| O | 23 | Oct 09/2008 | O | 5 | Oct 09/2008 | O | 8 | Oct 09/2008 |
| O | 24 | Oct 09/2008 | R | 6 | Oct 09/2008 | O | 9 | Oct 09/2008 |
| O | 25 | Oct 09/2008 | O | 7 | Oct 09/2008 | R | 10 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 1
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W0110 cont. | | | W0130 cont. | | | W0610 cont. | | |
| O | 11 | Oct 09/2008 | O | 4 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 12 | Oct 09/2008 | O | 5 | Oct 09/2008 | O W0630 | 1 | Oct 09/2008 |
| O | 13 | Oct 09/2008 | O | 6 | Oct 09/2008 | O W0800 | 1 | Oct 09/2008 |
| R | 14 | Oct 09/2008 | O | 7 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 15 | Oct 09/2008 | R | 8 | Oct 09/2008 | O W0810 | 1 | Oct 09/2008 |
| O | 16 | Oct 09/2008 | O | 9 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 17 | Oct 09/2008 | O W0200 | 1 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 18 | Oct 09/2008 | O W0440 | 1 | Oct 09/2008 | O W1000 | 1 | Oct 09/2008 |
| O W0120 | 1 | Oct 09/2008 | O | 2 | Oct 09/2008 | R | 2 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | O W0500 | 1 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 3 | Oct 09/2008 | O | 2 | Oct 09/2008 | O W1010 | 1 | Oct 09/2008 |
| O | 4 | Oct 09/2008 | O | 3 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| R | 5 | Oct 09/2008 | O | 4 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 6 | Oct 09/2008 | O W0510 | 1 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| R | 7 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| R | 8 | Oct 09/2008 | O | 3 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| O | 9 | Oct 09/2008 | O | 4 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| O | 10 | Oct 09/2008 | O | 5 | Oct 09/2008 | O | 8 | Oct 09/2008 |
| O | 11 | Oct 09/2008 | O W0520 | 1 | Oct 09/2008 | O W1020 | 1 | Oct 09/2008 |
| R | 12 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| R | 13 | Oct 09/2008 | O W0530 | 1 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 14 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| O | 15 | Oct 09/2008 | O W0540 | 1 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| O | 16 | Oct 09/2008 | O W0550 | 1 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| R W0130 | 1 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| R | 2 | Oct 09/2008 | O W0600 | 1 | Oct 09/2008 | O | 8 | Oct 09/2008 |
| O | 3 | Oct 09/2008 | O W0610 | 1 | Oct 09/2008 | O | 9 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 2
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|---------|------|-------------|-------------|------|-------------|
| W1020 cont. | | | W1120 | 1 | Jan 21/2005 | W1130 cont. | | |
| O | 10 | Oct 09/2008 | | 2 | Jan 21/2005 | | 3 | Jan 21/2005 |
| O | 11 | Oct 09/2008 | | 3 | Jan 21/2005 | | 4 | Jan 21/2005 |
| O | 12 | Oct 09/2008 | | 4 | Jan 21/2005 | | 5 | Jan 21/2005 |
| O | 13 | Oct 09/2008 | | 5 | Jan 21/2005 | | 6 | Jan 21/2005 |
| O | 14 | Oct 09/2008 | | 6 | Jan 21/2005 | | 7 | Jan 21/2005 |
| O | 15 | Oct 09/2008 | | 7 | Jan 21/2005 | | 8 | Jan 21/2005 |
| O | 16 | Oct 09/2008 | | 8 | Jan 21/2005 | | 9 | Jan 21/2005 |
| O | 17 | Oct 09/2008 | | 9 | Jan 21/2005 | | 10 | Jan 21/2005 |
| R | 18 | Oct 09/2008 | | 10 | Jan 21/2005 | | 11 | Jan 21/2005 |
| R | 19 | Oct 09/2008 | | 11 | Jan 21/2005 | | 12 | Jan 21/2005 |
| D | 20 | Oct 09/2008 | | 12 | Jan 21/2005 | | 13 | Jan 21/2005 |
| W1030 | 1 | Jan 21/2005 | | 13 | Jan 21/2005 | | 14 | Jan 21/2005 |
| | 2 | Jan 21/2005 | | 14 | Jan 21/2005 | | 15 | Jan 21/2005 |
| | 3 | Jan 21/2005 | | 15 | Jan 21/2005 | | 16 | Jan 21/2005 |
| | 4 | Jan 21/2005 | | 16 | Jan 21/2005 | | 17 | Jan 21/2005 |
| | 5 | Jan 21/2005 | | 17 | Jan 21/2005 | W1140 | 1 | Jan 21/2005 |
| | 6 | Jan 21/2005 | | 18 | Jan 21/2005 | | 2 | Jan 21/2005 |
| | 7 | Jan 21/2005 | | 19 | Jan 21/2005 | | 3 | Jan 21/2005 |
| | 8 | Jan 21/2005 | | 20 | Jan 21/2005 | | 4 | Jan 21/2005 |
| | 9 | Jan 21/2005 | | 21 | Jan 21/2005 | | 5 | Jan 21/2005 |
| | 10 | Jan 21/2005 | | 22 | Jan 21/2005 | | 6 | Jan 21/2005 |
| | 11 | Jan 21/2005 | | 23 | Jan 21/2005 | | 7 | Jan 21/2005 |
| | 12 | Jan 21/2005 | | 24 | Jan 21/2005 | | 8 | Jan 21/2005 |
| W1110 | 1 | Jan 21/2005 | | 25 | Jan 21/2005 | | 9 | Jan 21/2005 |
| | 2 | Jan 21/2005 | | 26 | Jan 21/2005 | | 10 | Jan 21/2005 |
| | 3 | Jan 21/2005 | W1130 | 1 | Jan 21/2005 | | 11 | Jan 21/2005 |
| | 4 | Jan 21/2005 | | 2 | Jan 21/2005 | W1160 | 1 | Jan 21/2005 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 3
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1160 cont. | | | W1160 cont. | | | W1170 cont. | | |
| | 2 | Jan 21/2005 | | 29 | Jan 21/2005 | | 9 | Jan 21/2005 |
| | 3 | Jan 21/2005 | | 30 | Jan 21/2005 | | 10 | Jan 21/2005 |
| | 4 | Jan 21/2005 | | 31 | Jan 21/2005 | R | 11 | Oct 09/2008 |
| | 5 | Jan 21/2005 | | 32 | Jan 21/2005 | O | 12 | Oct 09/2008 |
| | 6 | Jan 21/2005 | | 33 | Jan 21/2005 | R | 13 | Oct 09/2008 |
| | 7 | Jan 21/2005 | | 34 | Jan 21/2005 | O | 14 | Oct 09/2008 |
| | 8 | Jan 21/2005 | | 35 | Jan 21/2005 | O | 15 | Oct 09/2008 |
| | 9 | Jan 21/2005 | | 36 | Jan 21/2005 | R | 16 | Oct 09/2008 |
| | 10 | Jan 21/2005 | | 37 | Jan 21/2005 | R | 17 | Oct 09/2008 |
| | 11 | Jan 21/2005 | | 38 | Jan 21/2005 | O | 18 | Oct 09/2008 |
| | 12 | Jan 21/2005 | | 39 | Jan 21/2005 | R | 19 | Oct 09/2008 |
| | 13 | Jan 21/2005 | | 40 | Jan 21/2005 | R | 20 | Oct 09/2008 |
| | 14 | Jan 21/2005 | | 41 | Jan 21/2005 | O | 21 | Oct 09/2008 |
| | 15 | Jan 21/2005 | | 42 | Jan 21/2005 | O | 22 | Oct 09/2008 |
| | 16 | Jan 21/2005 | | 43 | Jan 21/2005 | O | 23 | Oct 09/2008 |
| | 17 | Jan 21/2005 | | 44 | Jan 21/2005 | O | 24 | Oct 09/2008 |
| | 18 | Jan 21/2005 | | 45 | Jan 21/2005 | O | 25 | Oct 09/2008 |
| | 19 | Jan 21/2005 | | 46 | Jan 21/2005 | O | 26 | Oct 09/2008 |
| | 20 | Jan 21/2005 | | 47 | Jan 21/2005 | O | 27 | Oct 09/2008 |
| | 21 | Jan 21/2005 | W1170 | 1 | Jan 21/2005 | O | 28 | Oct 09/2008 |
| | 22 | Jan 21/2005 | | 2 | Jan 21/2005 | O | 29 | Oct 09/2008 |
| | 23 | Jan 21/2005 | R | 3 | Oct 09/2008 | R | 30 | Oct 09/2008 |
| | 24 | Jan 21/2005 | | 4 | Jan 21/2005 | O | 31 | Oct 09/2008 |
| | 25 | Jan 21/2005 | R | 5 | Oct 09/2008 | O | 32 | Oct 09/2008 |
| | 26 | Jan 21/2005 | O | 6 | Oct 09/2008 | O | 33 | Oct 09/2008 |
| | 27 | Jan 21/2005 | R | 7 | Oct 09/2008 | R | 34 | Oct 09/2008 |
| | 28 | Jan 21/2005 | | 8 | Jan 21/2005 | O | 35 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 4
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1170 cont. | | | W1170 cont. | | | W1170 cont. | | |
| O | 36 | Oct 09/2008 | O | 63 | Oct 09/2008 | O | 90 | Oct 09/2008 |
| R | 37 | Oct 09/2008 | O | 64 | Oct 09/2008 | O | 91 | Oct 09/2008 |
| R | 38 | Oct 09/2008 | O | 65 | Oct 09/2008 | O | 92 | Oct 09/2008 |
| O | 39 | Oct 09/2008 | O | 66 | Oct 09/2008 | O | 93 | Oct 09/2008 |
| O | 40 | Oct 09/2008 | O | 67 | Oct 09/2008 | O | 94 | Oct 09/2008 |
| O | 41 | Oct 09/2008 | O | 68 | Oct 09/2008 | O | 95 | Oct 09/2008 |
| R | 42 | Oct 09/2008 | O | 69 | Oct 09/2008 | O | 96 | Oct 09/2008 |
| R | 43 | Oct 09/2008 | O | 70 | Oct 09/2008 | O | 97 | Oct 09/2008 |
| R | 44 | Oct 09/2008 | O | 71 | Oct 09/2008 | O | 98 | Oct 09/2008 |
| R | 45 | Oct 09/2008 | O | 72 | Oct 09/2008 | O | 99 | Oct 09/2008 |
| O | 46 | Oct 09/2008 | O | 73 | Oct 09/2008 | R | 100 | Oct 09/2008 |
| R | 47 | Oct 09/2008 | O | 74 | Oct 09/2008 | O | 101 | Oct 09/2008 |
| R | 48 | Oct 09/2008 | O | 75 | Oct 09/2008 | R | 102 | Oct 09/2008 |
| O | 49 | Oct 09/2008 | O | 76 | Oct 09/2008 | O | 103 | Oct 09/2008 |
| R | 50 | Oct 09/2008 | O | 77 | Oct 09/2008 | O | 104 | Oct 09/2008 |
| R | 51 | Oct 09/2008 | O | 78 | Oct 09/2008 | O | 105 | Oct 09/2008 |
| R | 52 | Oct 09/2008 | O | 79 | Oct 09/2008 | O | 106 | Oct 09/2008 |
| O | 53 | Oct 09/2008 | O | 80 | Oct 09/2008 | O | 107 | Oct 09/2008 |
| O | 54 | Oct 09/2008 | O | 81 | Oct 09/2008 | O | 108 | Oct 09/2008 |
| O | 55 | Oct 09/2008 | O | 82 | Oct 09/2008 | O | 109 | Oct 09/2008 |
| O | 56 | Oct 09/2008 | O | 83 | Oct 09/2008 | O | 110 | Oct 09/2008 |
| O | 57 | Oct 09/2008 | O | 84 | Oct 09/2008 | O | 111 | Oct 09/2008 |
| O | 58 | Oct 09/2008 | O | 85 | Oct 09/2008 | O | 112 | Oct 09/2008 |
| O | 59 | Oct 09/2008 | O | 86 | Oct 09/2008 | O | 113 | Oct 09/2008 |
| O | 60 | Oct 09/2008 | O | 87 | Oct 09/2008 | O | 114 | Oct 09/2008 |
| O | 61 | Oct 09/2008 | O | 88 | Oct 09/2008 | O | 115 | Oct 09/2008 |
| O | 62 | Oct 09/2008 | O | 89 | Oct 09/2008 | O | 116 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 5
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|---------|------|-------------|
| W1170 cont. | | | W1170 cont. | | | O W1230 | 1 | Oct 09/2008 |
| O | 117 | Oct 09/2008 | R | 144 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| R | 118 | Oct 09/2008 | O | 145 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 119 | Oct 09/2008 | O | 146 | Oct 09/2008 | R | 4 | Oct 09/2008 |
| O | 120 | Oct 09/2008 | O | 147 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| O | 121 | Oct 09/2008 | O | 148 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| O | 122 | Oct 09/2008 | O | 149 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| R | 123 | Oct 09/2008 | O | 150 | Oct 09/2008 | O | 8 | Oct 09/2008 |
| O | 124 | Oct 09/2008 | O | 151 | Oct 09/2008 | O | 9 | Oct 09/2008 |
| O | 125 | Oct 09/2008 | O | 152 | Oct 09/2008 | O | 10 | Oct 09/2008 |
| O | 126 | Oct 09/2008 | R | 153 | Oct 09/2008 | R | 11 | Oct 09/2008 |
| O | 127 | Oct 09/2008 | O | 154 | Oct 09/2008 | O | 12 | Oct 09/2008 |
| O | 128 | Oct 09/2008 | O | 155 | Oct 09/2008 | R | 13 | Oct 09/2008 |
| O | 129 | Oct 09/2008 | O | 156 | Oct 09/2008 | R | 14 | Oct 09/2008 |
| O | 130 | Oct 09/2008 | R | 157 | Oct 09/2008 | O | 15 | Oct 09/2008 |
| O | 131 | Oct 09/2008 | O | 158 | Oct 09/2008 | O | 16 | Oct 09/2008 |
| O | 132 | Oct 09/2008 | O | 159 | Oct 09/2008 | O | 17 | Oct 09/2008 |
| O | 133 | Oct 09/2008 | O | 160 | Oct 09/2008 | O | 18 | Oct 09/2008 |
| O | 134 | Oct 09/2008 | O | 161 | Oct 09/2008 | O W1240 | 1 | Oct 09/2008 |
| R | 135 | Oct 09/2008 | O | 162 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 136 | Oct 09/2008 | O | 163 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 137 | Oct 09/2008 | A | 164 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| O | 138 | Oct 09/2008 | A | 165 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| O | 139 | Oct 09/2008 | A | 166 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| O | 140 | Oct 09/2008 | O W1190 | 1 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| O | 141 | Oct 09/2008 | O | 2 | Oct 09/2008 | O W1250 | 1 | Oct 09/2008 |
| O | 142 | Oct 09/2008 | R | 3 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 143 | Oct 09/2008 | R | 4 | Oct 09/2008 | O | 3 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 6
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1250 cont. | | | W1260 cont. | | | W1260 cont. | | |
| O | 4 | Oct 09/2008 | O | 18 | Oct 09/2008 | O | 45 | Oct 09/2008 |
| O | 5 | Oct 09/2008 | O | 19 | Oct 09/2008 | O | 46 | Oct 09/2008 |
| O | 6 | Oct 09/2008 | O | 20 | Oct 09/2008 | O | 47 | Oct 09/2008 |
| O | 7 | Oct 09/2008 | O | 21 | Oct 09/2008 | R | 48 | Oct 09/2008 |
| O | 8 | Oct 09/2008 | O | 22 | Oct 09/2008 | O | 49 | Oct 09/2008 |
| O | 9 | Oct 09/2008 | O | 23 | Oct 09/2008 | R | 50 | Oct 09/2008 |
| R | 10 | Oct 09/2008 | O | 24 | Oct 09/2008 | O | 51 | Oct 09/2008 |
| O | 11 | Oct 09/2008 | O | 25 | Oct 09/2008 | O | 52 | Oct 09/2008 |
| O | 12 | Oct 09/2008 | O | 26 | Oct 09/2008 | O | 53 | Oct 09/2008 |
| O | 13 | Oct 09/2008 | R | 27 | Oct 09/2008 | O | 54 | Oct 09/2008 |
| O W1260 | 1 | Oct 09/2008 | O | 28 | Oct 09/2008 | O | 55 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | R | 29 | Oct 09/2008 | O | 56 | Oct 09/2008 |
| O | 3 | Oct 09/2008 | R | 30 | Oct 09/2008 | O | 57 | Oct 09/2008 |
| O | 4 | Oct 09/2008 | O | 31 | Oct 09/2008 | O | 58 | Oct 09/2008 |
| O | 5 | Oct 09/2008 | O | 32 | Oct 09/2008 | O | 59 | Oct 09/2008 |
| O | 6 | Oct 09/2008 | O | 33 | Oct 09/2008 | O | 60 | Oct 09/2008 |
| O | 7 | Oct 09/2008 | O | 34 | Oct 09/2008 | O | 61 | Oct 09/2008 |
| O | 8 | Oct 09/2008 | O | 35 | Oct 09/2008 | O | 62 | Oct 09/2008 |
| O | 9 | Oct 09/2008 | O | 36 | Oct 09/2008 | O | 63 | Oct 09/2008 |
| O | 10 | Oct 09/2008 | O | 37 | Oct 09/2008 | O | 64 | Oct 09/2008 |
| O | 11 | Oct 09/2008 | O | 38 | Oct 09/2008 | O | 65 | Oct 09/2008 |
| O | 12 | Oct 09/2008 | O | 39 | Oct 09/2008 | O | 66 | Oct 09/2008 |
| O | 13 | Oct 09/2008 | O | 40 | Oct 09/2008 | O | 67 | Oct 09/2008 |
| O | 14 | Oct 09/2008 | O | 41 | Oct 09/2008 | O | 68 | Oct 09/2008 |
| O | 15 | Oct 09/2008 | O | 42 | Oct 09/2008 | O | 69 | Oct 09/2008 |
| O | 16 | Oct 09/2008 | O | 43 | Oct 09/2008 | O | 70 | Oct 09/2008 |
| O | 17 | Oct 09/2008 | O | 44 | Oct 09/2008 | O | 71 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 7
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1260 cont. | | | W1270 cont. | | | W1270 cont. | | |
| O | 72 | Oct 09/2008 | O | 25 | Oct 09/2008 | O | 52 | Oct 09/2008 |
| O | 73 | Oct 09/2008 | O | 26 | Oct 09/2008 | O | 53 | Oct 09/2008 |
| A | 74 | Oct 09/2008 | O | 27 | Oct 09/2008 | O | 54 | Oct 09/2008 |
| W1270 | 1 | Jan 21/2005 | O | 28 | Oct 09/2008 | R | 55 | Oct 09/2008 |
| | 2 | Jan 21/2005 | O | 29 | Oct 09/2008 | R | 56 | Oct 09/2008 |
| | 3 | Jan 21/2005 | R | 30 | Oct 09/2008 | O | 57 | Oct 09/2008 |
| | 4 | Jan 21/2005 | R | 31 | Oct 09/2008 | O | 58 | Oct 09/2008 |
| | 5 | Jan 21/2005 | R | 32 | Oct 09/2008 | O | 59 | Oct 09/2008 |
| | 6 | Jan 21/2005 | R | 33 | Oct 09/2008 | R | 60 | Oct 09/2008 |
| | 7 | Jan 21/2005 | O | 34 | Oct 09/2008 | O | 61 | Oct 09/2008 |
| | 8 | Jan 21/2005 | O | 35 | Oct 09/2008 | O | 62 | Oct 09/2008 |
| | 9 | Jan 21/2005 | O | 36 | Oct 09/2008 | O | 63 | Oct 09/2008 |
| | 10 | Jan 21/2005 | O | 37 | Oct 09/2008 | O | 64 | Oct 09/2008 |
| | 11 | Jan 21/2005 | O | 38 | Oct 09/2008 | O | 65 | Oct 09/2008 |
| | 12 | Jan 21/2005 | O | 39 | Oct 09/2008 | O | 66 | Oct 09/2008 |
| | 13 | Jan 21/2005 | O | 40 | Oct 09/2008 | O | 67 | Oct 09/2008 |
| O | 14 | Oct 09/2008 | O | 41 | Oct 09/2008 | O | 68 | Oct 09/2008 |
| O | 15 | Oct 09/2008 | O | 42 | Oct 09/2008 | O | 69 | Oct 09/2008 |
| O | 16 | Oct 09/2008 | O | 43 | Oct 09/2008 | O | 70 | Oct 09/2008 |
| O | 17 | Oct 09/2008 | R | 44 | Oct 09/2008 | O | 71 | Oct 09/2008 |
| O | 18 | Oct 09/2008 | O | 45 | Oct 09/2008 | O | 72 | Oct 09/2008 |
| O | 19 | Oct 09/2008 | O | 46 | Oct 09/2008 | O | 73 | Oct 09/2008 |
| O | 20 | Oct 09/2008 | O | 47 | Oct 09/2008 | R | 74 | Oct 09/2008 |
| O | 21 | Oct 09/2008 | O | 48 | Oct 09/2008 | R | 75 | Oct 09/2008 |
| O | 22 | Oct 09/2008 | R | 49 | Oct 09/2008 | R | 76 | Oct 09/2008 |
| O | 23 | Oct 09/2008 | O | 50 | Oct 09/2008 | R | 77 | Oct 09/2008 |
| O | 24 | Oct 09/2008 | O | 51 | Oct 09/2008 | R | 78 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 8
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1270 cont. | | | W1270 cont. | | | W1270 cont. | | |
| O | 79 | Oct 09/2008 | O | 106 | Oct 09/2008 | O | 133 | Oct 09/2008 |
| O | 80 | Oct 09/2008 | O | 107 | Oct 09/2008 | O | 134 | Oct 09/2008 |
| O | 81 | Oct 09/2008 | O | 108 | Oct 09/2008 | O | 135 | Oct 09/2008 |
| R | 82 | Oct 09/2008 | O | 109 | Oct 09/2008 | O | 136 | Oct 09/2008 |
| O | 83 | Oct 09/2008 | O | 110 | Oct 09/2008 | O | 137 | Oct 09/2008 |
| O | 84 | Oct 09/2008 | O | 111 | Oct 09/2008 | O | 138 | Oct 09/2008 |
| O | 85 | Oct 09/2008 | O | 112 | Oct 09/2008 | O | 139 | Oct 09/2008 |
| O | 86 | Oct 09/2008 | O | 113 | Oct 09/2008 | O | 140 | Oct 09/2008 |
| O | 87 | Oct 09/2008 | O | 114 | Oct 09/2008 | O | 141 | Oct 09/2008 |
| O | 88 | Oct 09/2008 | O | 115 | Oct 09/2008 | O | 142 | Oct 09/2008 |
| O | 89 | Oct 09/2008 | O | 116 | Oct 09/2008 | O | 143 | Oct 09/2008 |
| O | 90 | Oct 09/2008 | O | 117 | Oct 09/2008 | R | 144 | Oct 09/2008 |
| O | 91 | Oct 09/2008 | O | 118 | Oct 09/2008 | O | 145 | Oct 09/2008 |
| O | 92 | Oct 09/2008 | O | 119 | Oct 09/2008 | O | 146 | Oct 09/2008 |
| O | 93 | Oct 09/2008 | O | 120 | Oct 09/2008 | R | 147 | Oct 09/2008 |
| O | 94 | Oct 09/2008 | O | 121 | Oct 09/2008 | R | 148 | Oct 09/2008 |
| O | 95 | Oct 09/2008 | O | 122 | Oct 09/2008 | O | 149 | Oct 09/2008 |
| O | 96 | Oct 09/2008 | O | 123 | Oct 09/2008 | O | 150 | Oct 09/2008 |
| O | 97 | Oct 09/2008 | R | 124 | Oct 09/2008 | O | 151 | Oct 09/2008 |
| O | 98 | Oct 09/2008 | O | 125 | Oct 09/2008 | O | 152 | Oct 09/2008 |
| O | 99 | Oct 09/2008 | R | 126 | Oct 09/2008 | O | 153 | Oct 09/2008 |
| O | 100 | Oct 09/2008 | O | 127 | Oct 09/2008 | O | 154 | Oct 09/2008 |
| O | 101 | Oct 09/2008 | O | 128 | Oct 09/2008 | R | 155 | Oct 09/2008 |
| O | 102 | Oct 09/2008 | O | 129 | Oct 09/2008 | A | 156 | Oct 09/2008 |
| O | 103 | Oct 09/2008 | R | 130 | Oct 09/2008 | A | 157 | Oct 09/2008 |
| O | 104 | Oct 09/2008 | R | 131 | Oct 09/2008 | W1280 | 1 | May 17/2006 |
| O | 105 | Oct 09/2008 | O | 132 | Oct 09/2008 | | 2 | May 17/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 9
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1280 cont. | | | W1280 cont. | | | W1280 cont. | | |
| | 3 | May 17/2006 | O | 30 | Oct 09/2008 | A | 57 | Oct 09/2008 |
| | 4 | Dec 18/2007 | O | 31 | Oct 09/2008 | O W1310 | 1 | Oct 09/2008 |
| | 5 | May 17/2006 | O | 32 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| | 6 | May 17/2006 | O | 33 | Oct 09/2008 | O W1320 | 1 | Oct 09/2008 |
| | 7 | May 17/2006 | O | 34 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| | 8 | May 17/2006 | O | 35 | Oct 09/2008 | O W1330 | 1 | Oct 09/2008 |
| | 9 | May 17/2006 | R | 36 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| | 10 | May 17/2006 | O | 37 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| | 11 | May 17/2006 | O | 38 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| | 12 | May 17/2006 | O | 39 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| | 13 | May 17/2006 | O | 40 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| | 14 | May 17/2006 | O | 41 | Oct 09/2008 | O W1420 | 1 | Oct 09/2008 |
| | 15 | May 17/2006 | O | 42 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| | 16 | May 17/2006 | O | 43 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| | 17 | May 17/2006 | O | 44 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| | 18 | May 17/2006 | O | 45 | Oct 09/2008 | R | 5 | Oct 09/2008 |
| | 19 | May 17/2006 | O | 46 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| | 20 | May 17/2006 | O | 47 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| | 21 | May 17/2006 | O | 48 | Oct 09/2008 | O | 8 | Oct 09/2008 |
| | 22 | May 17/2006 | O | 49 | Oct 09/2008 | O | 9 | Oct 09/2008 |
| | 23 | May 17/2006 | O | 50 | Oct 09/2008 | O | 10 | Oct 09/2008 |
| | 24 | May 17/2006 | O | 51 | Oct 09/2008 | O | 11 | Oct 09/2008 |
| | 25 | May 17/2006 | O | 52 | Oct 09/2008 | O | 12 | Oct 09/2008 |
| | 26 | May 17/2006 | O | 53 | Oct 09/2008 | O W1430 | 1 | Oct 09/2008 |
| | 27 | May 17/2006 | O | 54 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| R | 28 | Oct 09/2008 | O | 55 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 29 | Oct 09/2008 | O | 56 | Oct 09/2008 | O | 4 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 10
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W1430 cont. | | | W1450 cont. | | | W2020 cont. | | |
| O | 5 | Oct 09/2008 | O | 5 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 6 | Oct 09/2008 | O | 6 | Oct 09/2008 | O W2030 | 1 | Oct 09/2008 |
| O | 7 | Oct 09/2008 | O | 7 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 8 | Oct 09/2008 | O | 8 | Oct 09/2008 | O W2040 | 1 | Oct 09/2008 |
| O | 9 | Oct 09/2008 | O | 9 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 10 | Oct 09/2008 | O | 10 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 11 | Oct 09/2008 | O | 11 | Oct 09/2008 | O W2050 | 1 | Oct 09/2008 |
| O | 12 | Oct 09/2008 | O | 12 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 13 | Oct 09/2008 | O | 13 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 14 | Oct 09/2008 | O | 14 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| O | 15 | Oct 09/2008 | O | 15 | Oct 09/2008 | O W2060 | 1 | Oct 09/2008 |
| O | 16 | Oct 09/2008 | O | 16 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 17 | Oct 09/2008 | O | 17 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 18 | Oct 09/2008 | O | 18 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| O | 19 | Oct 09/2008 | O | 19 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| O | 20 | Oct 09/2008 | O | 20 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| O | 21 | Oct 09/2008 | O | 21 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| O | 22 | Oct 09/2008 | O W1500 | 1 | Oct 09/2008 | R | 8 | Oct 09/2008 |
| O | 23 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 9 | Oct 09/2008 |
| O | 24 | Oct 09/2008 | O | 3 | Oct 09/2008 | O | 10 | Oct 09/2008 |
| O | 25 | Oct 09/2008 | O | 4 | Oct 09/2008 | O | 11 | Oct 09/2008 |
| O | 26 | Oct 09/2008 | O W2000 | 1 | Oct 09/2008 | O | 12 | Oct 09/2008 |
| O | 27 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 13 | Oct 09/2008 |
| O W1450 | 1 | Oct 09/2008 | O W2010 | 1 | Oct 09/2008 | R | 14 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | O | 2 | Oct 09/2008 | R | 15 | Oct 09/2008 |
| O | 3 | Oct 09/2008 | O W2020 | 1 | Oct 09/2008 | O | 16 | Oct 09/2008 |
| O | 4 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 17 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 11
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|---------|------|-------------|
| W2060 cont. | | | W2070 cont. | | | W2090 | 1 | May 17/2006 |
| O | 18 | Oct 09/2008 | O | 20 | Oct 09/2008 | W2130 | 1 | May 17/2006 |
| O | 19 | Oct 09/2008 | O | 21 | Oct 09/2008 | | 2 | May 17/2006 |
| O | 20 | Oct 09/2008 | O | 22 | Oct 09/2008 | W2140 | 1 | May 17/2006 |
| R | 21 | Oct 09/2008 | O | 23 | Oct 09/2008 | W2150 | 1 | May 17/2006 |
| O | 22 | Oct 09/2008 | R | 24 | Oct 09/2008 | | 2 | May 17/2006 |
| O | 23 | Oct 09/2008 | O | 25 | Oct 09/2008 | | 3 | May 17/2006 |
| O | 24 | Oct 09/2008 | O | 26 | Oct 09/2008 | | 4 | May 17/2006 |
| O | 25 | Oct 09/2008 | O | 27 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| O | 1 | Oct 09/2008 | O | 28 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | O | 29 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| O | 3 | Oct 09/2008 | O | 30 | Oct 09/2008 | R | 8 | Oct 09/2008 |
| O | 4 | Oct 09/2008 | O | 31 | Oct 09/2008 | W2190 | 1 | May 17/2006 |
| O | 5 | Oct 09/2008 | O | 32 | Oct 09/2008 | | 2 | May 17/2006 |
| O | 6 | Oct 09/2008 | O | 33 | Oct 09/2008 | W2220 | 1 | May 17/2006 |
| O | 7 | Oct 09/2008 | O | 34 | Oct 09/2008 | | 2 | May 17/2006 |
| O | 8 | Oct 09/2008 | O | 35 | Oct 09/2008 | | 3 | May 17/2006 |
| R | 9 | Oct 09/2008 | O | 36 | Oct 09/2008 | | 4 | May 17/2006 |
| R | 10 | Oct 09/2008 | O | 37 | Oct 09/2008 | | 5 | May 17/2006 |
| R | 11 | Oct 09/2008 | O | 38 | Oct 09/2008 | W2230 | 1 | May 17/2006 |
| O | 12 | Oct 09/2008 | O | 39 | Oct 09/2008 | W2240 | 1 | May 17/2006 |
| O | 13 | Oct 09/2008 | O | 40 | Oct 09/2008 | | 2 | May 17/2006 |
| O | 14 | Oct 09/2008 | O | 41 | Oct 09/2008 | | 3 | May 17/2006 |
| R | 15 | Oct 09/2008 | O | 42 | Oct 09/2008 | | 4 | May 17/2006 |
| O | 16 | Oct 09/2008 | O | 43 | Oct 09/2008 | R | 5 | Oct 09/2008 |
| O | 17 | Oct 09/2008 | A | 44 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| R | 18 | Oct 09/2008 | W2080 | 1 | May 17/2006 | O | 7 | Oct 09/2008 |
| O | 19 | Oct 09/2008 | | 2 | May 17/2006 | O | 8 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 12
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|---------|------|-------------|---------|------|-------------|
| W2240 cont. | | | W2260 | 1 | May 17/2006 | R W2330 | 1 | Oct 09/2008 |
| O | 9 | Oct 09/2008 | | 2 | May 17/2006 | R | 2 | Oct 09/2008 |
| R | 10 | Oct 09/2008 | W2270 | 1 | May 17/2006 | R | 3 | Oct 09/2008 |
| O | 11 | Oct 09/2008 | W2290 | 1 | May 17/2006 | O | 4 | Oct 09/2008 |
| O | 12 | Oct 09/2008 | | 2 | Dec 18/2007 | O | 5 | Oct 09/2008 |
| O | 13 | Oct 09/2008 | | 3 | Dec 18/2007 | O | 6 | Oct 09/2008 |
| O | 14 | Oct 09/2008 | | 4 | Dec 18/2007 | W2340 | 1 | May 17/2006 |
| O | 15 | Oct 09/2008 | | 5 | Dec 18/2007 | | 2 | May 17/2006 |
| O | 16 | Oct 09/2008 | | 6 | Dec 18/2007 | | 3 | May 17/2006 |
| O | 17 | Oct 09/2008 | W2300 | 1 | May 17/2006 | | 4 | May 17/2006 |
| O W2250 | 1 | Oct 09/2008 | | 2 | May 17/2006 | | 5 | May 17/2006 |
| O | 2 | Oct 09/2008 | | 3 | May 17/2006 | W2350 | 1 | May 17/2006 |
| R | 3 | Oct 09/2008 | | 4 | May 17/2006 | R | 2 | Oct 09/2008 |
| | 4 | May 17/2006 | | 5 | May 17/2006 | O | 3 | Oct 09/2008 |
| | 5 | May 17/2006 | | 6 | May 17/2006 | O | 4 | Oct 09/2008 |
| | 6 | May 17/2006 | W2310 | 1 | May 17/2006 | O | 5 | Oct 09/2008 |
| R | 7 | Oct 09/2008 | | 2 | May 17/2006 | O | 6 | Oct 09/2008 |
| O | 8 | Oct 09/2008 | | 3 | May 17/2006 | O | 7 | Oct 09/2008 |
| R | 9 | Oct 09/2008 | | 4 | May 17/2006 | | 8 | May 17/2006 |
| O | 10 | Oct 09/2008 | | 5 | May 17/2006 | | 9 | May 17/2006 |
| O | 11 | Oct 09/2008 | W2320 | 1 | May 17/2006 | | 10 | May 17/2006 |
| O | 12 | Oct 09/2008 | | 2 | May 17/2006 | | 11 | Dec 18/2007 |
| O | 13 | Oct 09/2008 | | 3 | May 17/2006 | | 12 | May 17/2006 |
| O | 14 | Oct 09/2008 | | 4 | May 17/2006 | | 13 | May 17/2006 |
| O | 15 | Oct 09/2008 | | 5 | May 17/2006 | | 14 | Dec 18/2007 |
| O | 16 | Oct 09/2008 | | 6 | May 17/2006 | | 15 | May 17/2006 |
| O | 17 | Oct 09/2008 | | 7 | May 17/2006 | | 16 | May 17/2006 |
| O | 18 | Oct 09/2008 | | 8 | May 17/2006 | | 17 | May 17/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 13
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|---------|------|-------------|-------------|------|-------------|
| W2350 cont. | | | W2400 | 1 | May 17/2006 | W2500 cont. | | |
| | 18 | May 17/2006 | | 2 | May 17/2006 | | 2 | May 17/2006 |
| | 19 | May 17/2006 | | 3 | May 17/2006 | | 3 | May 17/2006 |
| | 20 | May 17/2006 | | 4 | May 17/2006 | | 4 | May 17/2006 |
| | 21 | May 17/2006 | | 5 | May 17/2006 | | 5 | May 17/2006 |
| | 22 | May 17/2006 | | 6 | May 17/2006 | | 6 | May 17/2006 |
| | 23 | May 17/2006 | W2410 | 1 | May 17/2006 | | 7 | May 17/2006 |
| | 24 | May 17/2006 | | 2 | May 17/2006 | W2510 | 1 | May 17/2006 |
| | 25 | May 17/2006 | | 3 | May 17/2006 | | 2 | May 17/2006 |
| R | 26 | Oct 09/2008 | | 4 | May 17/2006 | | 3 | May 17/2006 |
| O | 27 | Oct 09/2008 | | 5 | May 17/2006 | | 4 | May 17/2006 |
| O | 28 | Oct 09/2008 | | 6 | May 17/2006 | | 5 | May 17/2006 |
| O | 29 | Oct 09/2008 | | 7 | May 17/2006 | | 6 | May 17/2006 |
| W2360 | 1 | May 17/2006 | | 8 | May 17/2006 | | 7 | May 17/2006 |
| | 2 | May 17/2006 | | 9 | May 17/2006 | | 8 | May 17/2006 |
| | 3 | May 17/2006 | | 10 | May 17/2006 | | 9 | May 17/2006 |
| O | 4 | Oct 09/2008 | | 11 | May 17/2006 | | 10 | May 17/2006 |
| O | 5 | Oct 09/2008 | | 12 | May 17/2006 | | 11 | May 17/2006 |
| O | 6 | Oct 09/2008 | | 13 | May 17/2006 | W2520 | 1 | May 17/2006 |
| O | 7 | Oct 09/2008 | | 14 | May 17/2006 | W2600 | 1 | May 17/2006 |
| W2370 | 1 | May 17/2006 | W2440 | 1 | May 17/2006 | | 2 | May 17/2006 |
| | 2 | May 17/2006 | | 2 | May 17/2006 | | 3 | May 17/2006 |
| W2380 | 1 | May 17/2006 | | 3 | May 17/2006 | | 4 | May 17/2006 |
| | 2 | May 17/2006 | | 4 | May 17/2006 | | 5 | May 17/2006 |
| | 3 | May 17/2006 | | 5 | May 17/2006 | | 6 | May 17/2006 |
| | 4 | May 17/2006 | | 6 | May 17/2006 | W2610 | 1 | May 17/2006 |
| W2390 | 1 | May 17/2006 | W2450 | 1 | May 17/2006 | | 2 | May 17/2006 |
| | 2 | May 17/2006 | W2500 | 1 | May 17/2006 | | 3 | May 17/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 14
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W2610 cont. | | | W2650 cont. | | | W2810 cont. | | |
| | 4 | May 17/2006 | O | 9 | Oct 09/2008 | | 3 | May 17/2006 |
| | 5 | May 17/2006 | O | 10 | Oct 09/2008 | | 4 | May 17/2006 |
| W2620 | 1 | May 17/2006 | W2660 | 1 | May 17/2006 | | 5 | May 17/2006 |
| | 2 | May 17/2006 | | 2 | May 17/2006 | W2820 | 1 | May 17/2006 |
| | 3 | May 17/2006 | | 3 | May 17/2006 | | 2 | May 17/2006 |
| | 4 | May 17/2006 | | 4 | May 17/2006 | | 3 | May 17/2006 |
| | 5 | May 17/2006 | W2680 | 1 | May 17/2006 | | 4 | May 17/2006 |
| | 6 | May 17/2006 | W2700 | 1 | May 17/2006 | W2830 | 1 | May 17/2006 |
| W2630 | 1 | May 17/2006 | R | 2 | Oct 09/2008 | W2840 | 1 | May 17/2006 |
| | 2 | May 17/2006 | O | 3 | Oct 09/2008 | | 2 | May 17/2006 |
| | 3 | May 17/2006 | O | 4 | Oct 09/2008 | | 3 | May 17/2006 |
| | 4 | May 17/2006 | O | 5 | Oct 09/2008 | W2850 | 1 | May 17/2006 |
| | 5 | May 17/2006 | W2710 | 1 | May 17/2006 | W2860 | 1 | May 17/2006 |
| | 6 | May 17/2006 | | 2 | May 17/2006 | W2880 | 1 | May 17/2006 |
| W2640 | 1 | May 17/2006 | | 3 | May 17/2006 | W3000 | 1 | May 17/2006 |
| | 2 | May 17/2006 | | 4 | May 17/2006 | W3010 | 1 | May 17/2006 |
| | 3 | May 17/2006 | | 5 | May 17/2006 | W3020 | 1 | May 17/2006 |
| | 4 | May 17/2006 | W2720 | 1 | May 17/2006 | W3030 | 1 | May 17/2006 |
| | 5 | May 17/2006 | | 2 | May 17/2006 | W3050 | 1 | May 17/2006 |
| W2650 | 1 | May 17/2006 | | 3 | May 17/2006 | | 2 | May 17/2006 |
| O | 2 | Oct 09/2008 | W2730 | 1 | May 17/2006 | | 3 | May 17/2006 |
| O | 3 | Oct 09/2008 | W2800 | 1 | May 17/2006 | | 4 | May 17/2006 |
| O | 4 | Oct 09/2008 | | 2 | May 17/2006 | W3060 | 1 | May 17/2006 |
| O | 5 | Oct 09/2008 | | 3 | May 17/2006 | W3100 | 1 | May 17/2006 |
| O | 6 | Oct 09/2008 | | 4 | May 17/2006 | | 2 | May 17/2006 |
| O | 7 | Oct 09/2008 | W2810 | 1 | May 17/2006 | | 3 | May 17/2006 |
| O | 8 | Oct 09/2008 | | 2 | May 17/2006 | W3110 | 1 | May 17/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 15
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|---------|------|-------------|
| W3110 cont. | | | W3340 cont. | | | W3430 | 1 | May 17/2006 |
| | 2 | May 17/2006 | | 3 | May 17/2006 | W3440 | 1 | May 17/2006 |
| W3120 | 1 | May 17/2006 | W3360 | 1 | May 17/2006 | W3450 | 1 | May 17/2006 |
| W3130 | 1 | May 17/2006 | W3370 | 1 | May 17/2006 | W3460 | 1 | May 17/2006 |
| | 2 | May 17/2006 | W3380 | 1 | May 17/2006 | | 2 | May 17/2006 |
| W3200 | 1 | May 17/2006 | | 2 | May 17/2006 | | 3 | May 17/2006 |
| | 2 | May 17/2006 | W3400 | 1 | May 17/2006 | W3470 | 1 | May 17/2006 |
| W3300 | 1 | May 17/2006 | | 2 | May 17/2006 | W3480 | 1 | May 17/2006 |
| | 2 | May 17/2006 | | 3 | May 17/2006 | | 2 | May 17/2006 |
| | 3 | May 17/2006 | | 4 | May 17/2006 | W3500 | 1 | May 17/2006 |
| | 4 | May 17/2006 | | 5 | May 17/2006 | W3510 | 1 | May 17/2006 |
| | 5 | May 17/2006 | | 6 | May 17/2006 | | 2 | May 17/2006 |
| | 6 | May 17/2006 | | 7 | May 17/2006 | | 3 | May 17/2006 |
| | 7 | May 17/2006 | | 8 | May 17/2006 | | 4 | May 17/2006 |
| | 8 | May 17/2006 | | 9 | May 17/2006 | | 5 | May 17/2006 |
| | 9 | May 17/2006 | R | 10 | Oct 09/2008 | | 6 | May 17/2006 |
| R | 10 | Oct 09/2008 | O | 11 | Oct 09/2008 | | 7 | May 17/2006 |
| O | 11 | Oct 09/2008 | W3410 | 1 | May 17/2006 | W3520 | 1 | May 17/2006 |
| | 1 | May 17/2006 | | 2 | May 17/2006 | W3530 | 1 | May 17/2006 |
| W3310 | 2 | May 17/2006 | | 3 | May 17/2006 | | 2 | May 17/2006 |
| | 3 | May 17/2006 | W3420 | 1 | May 17/2006 | | 3 | May 17/2006 |
| | 4 | May 17/2006 | | 2 | May 17/2006 | | 4 | May 17/2006 |
| W3320 | 1 | May 17/2006 | | 3 | May 17/2006 | | 5 | May 17/2006 |
| | 2 | May 17/2006 | | 4 | May 17/2006 | | 6 | May 17/2006 |
| | 3 | May 17/2006 | | 5 | May 17/2006 | | 7 | May 17/2006 |
| W3330 | 1 | May 17/2006 | | 6 | May 17/2006 | W3540 | 1 | May 17/2006 |
| R W3340 | 1 | Oct 09/2008 | | 7 | May 17/2006 | W3560 | 1 | May 17/2006 |
| R | 2 | Oct 09/2008 | | 8 | May 17/2006 | W3570 | 1 | May 17/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 16
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|---------|------|-------------|-------------|------|-------------|
| W3570 cont. | | | W3640 | 1 | May 17/2006 | W3700 cont. | | |
| | 2 | May 17/2006 | | 2 | May 17/2006 | | 14 | May 17/2006 |
| | 3 | May 17/2006 | W3650 | 1 | May 17/2006 | | 15 | May 17/2006 |
| | 4 | May 17/2006 | W3660 | 1 | May 17/2006 | | 16 | May 17/2006 |
| | 5 | May 17/2006 | W3670 | 1 | May 17/2006 | | 17 | May 17/2006 |
| | 6 | May 17/2006 | | 2 | May 17/2006 | | 18 | May 17/2006 |
| | 7 | May 17/2006 | | 3 | May 17/2006 | | 19 | May 17/2006 |
| | 8 | May 17/2006 | | 4 | May 17/2006 | | 20 | May 17/2006 |
| | 9 | May 17/2006 | | 5 | May 17/2006 | | 21 | May 17/2006 |
| | 10 | May 17/2006 | | 6 | May 17/2006 | | 22 | May 17/2006 |
| W3580 | 1 | May 17/2006 | | 7 | May 17/2006 | | 23 | May 17/2006 |
| | 2 | May 17/2006 | | 8 | May 17/2006 | | 24 | May 17/2006 |
| | 3 | May 17/2006 | W3680 | 1 | May 17/2006 | | 25 | May 17/2006 |
| W3590 | 1 | May 17/2006 | | 2 | May 17/2006 | | 26 | May 17/2006 |
| W3610 | 1 | May 17/2006 | W3690 | 1 | May 17/2006 | | 27 | May 17/2006 |
| | 2 | May 17/2006 | W3700 | 1 | May 17/2006 | | 28 | May 17/2006 |
| | 3 | May 17/2006 | | 2 | May 17/2006 | | 29 | May 17/2006 |
| | 4 | May 17/2006 | | 3 | May 17/2006 | | 30 | May 17/2006 |
| | 5 | May 17/2006 | | 4 | May 17/2006 | | 31 | May 17/2006 |
| | 6 | May 17/2006 | | 5 | May 17/2006 | | 32 | May 17/2006 |
| | 7 | May 17/2006 | | 6 | May 17/2006 | | 33 | May 17/2006 |
| W3630 | 1 | May 17/2006 | | 7 | May 17/2006 | | 34 | May 17/2006 |
| | 2 | May 17/2006 | | 8 | May 17/2006 | | 35 | May 17/2006 |
| | 3 | May 17/2006 | | 9 | May 17/2006 | | 36 | May 17/2006 |
| | 4 | May 17/2006 | | 10 | May 17/2006 | | 37 | May 17/2006 |
| | 5 | May 17/2006 | | 11 | May 17/2006 | | 38 | May 17/2006 |
| | 6 | May 17/2006 | | 12 | May 17/2006 | | 39 | May 17/2006 |
| | 7 | May 17/2006 | | 13 | May 17/2006 | | 40 | May 17/2006 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 17
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W3700 cont. | | | W3800 cont. | | | W3800 cont. | | |
| | 41 | May 17/2006 | | 13 | May 17/2006 | | 40 | May 17/2006 |
| | 42 | May 17/2006 | | 14 | May 17/2006 | | 41 | May 17/2006 |
| | 43 | May 17/2006 | | 15 | May 17/2006 | | 42 | May 17/2006 |
| | 44 | May 17/2006 | | 16 | May 17/2006 | | 43 | May 17/2006 |
| | 45 | May 17/2006 | | 17 | May 17/2006 | | 44 | May 17/2006 |
| | 46 | May 17/2006 | | 18 | May 17/2006 | W3820 | 1 | May 17/2006 |
| | 47 | May 17/2006 | | 19 | May 17/2006 | | 2 | May 17/2006 |
| | 48 | May 17/2006 | | 20 | May 17/2006 | W4000 | 1 | May 17/2006 |
| | 49 | May 17/2006 | | 21 | May 17/2006 | | 2 | May 17/2006 |
| | 50 | May 17/2006 | | 22 | May 17/2006 | | 3 | May 17/2006 |
| | 51 | May 17/2006 | | 23 | May 17/2006 | | 4 | May 17/2006 |
| | 52 | May 17/2006 | | 24 | May 17/2006 | | 5 | May 17/2006 |
| | 53 | May 17/2006 | | 25 | May 17/2006 | | 6 | May 17/2006 |
| W3720 | 1 | May 17/2006 | | 26 | May 17/2006 | | 7 | May 17/2006 |
| | 2 | May 17/2006 | | 27 | May 17/2006 | | 8 | May 17/2006 |
| W3800 | 1 | May 17/2006 | | 28 | May 17/2006 | | 9 | May 17/2006 |
| | 2 | May 17/2006 | | 29 | May 17/2006 | | 10 | May 17/2006 |
| | 3 | May 17/2006 | | 30 | May 17/2006 | W4010 | 1 | May 17/2006 |
| | 4 | May 17/2006 | | 31 | May 17/2006 | R W4020 | 1 | Oct 09/2008 |
| | 5 | May 17/2006 | | 32 | May 17/2006 | O | 2 | Oct 09/2008 |
| | 6 | May 17/2006 | | 33 | May 17/2006 | O | 3 | Oct 09/2008 |
| | 7 | May 17/2006 | | 34 | May 17/2006 | O | 4 | Oct 09/2008 |
| | 8 | May 17/2006 | | 35 | May 17/2006 | A W4030 | 1 | Oct 09/2008 |
| | 9 | May 17/2006 | | 36 | May 17/2006 | O W4040 | 1 | Oct 09/2008 |
| | 10 | May 17/2006 | | 37 | May 17/2006 | O W4050 | 1 | Oct 09/2008 |
| | 11 | May 17/2006 | | 38 | May 17/2006 | O | 2 | Oct 09/2008 |
| | 12 | May 17/2006 | | 39 | May 17/2006 | O W4060 | 1 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 18
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W4060 cont. | | | W4200 cont. | | | W4210 cont. | | |
| O | 2 | Oct 09/2008 | O | 7 | Oct 09/2008 | R | 19 | Oct 09/2008 |
| O W4070 | 1 | Oct 09/2008 | O | 8 | Oct 09/2008 | O | 20 | Oct 09/2008 |
| O W4080 | 1 | Oct 09/2008 | O | 9 | Oct 09/2008 | O | 21 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | O | 10 | Oct 09/2008 | O W4220 | 1 | Oct 09/2008 |
| O W4100 | 1 | Oct 09/2008 | O | 11 | Oct 09/2008 | O | 2 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | R | 12 | Oct 09/2008 | O | 3 | Oct 09/2008 |
| O | 3 | Oct 09/2008 | O | 13 | Oct 09/2008 | O | 4 | Oct 09/2008 |
| O | 4 | Oct 09/2008 | O | 14 | Oct 09/2008 | O | 5 | Oct 09/2008 |
| O | 5 | Oct 09/2008 | O | 15 | Oct 09/2008 | O | 6 | Oct 09/2008 |
| O | 6 | Oct 09/2008 | O W4210 | 1 | Oct 09/2008 | O | 7 | Oct 09/2008 |
| O | 7 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 8 | Oct 09/2008 |
| O | 8 | Oct 09/2008 | O | 3 | Oct 09/2008 | O | 9 | Oct 09/2008 |
| O | 9 | Oct 09/2008 | O | 4 | Oct 09/2008 | O | 10 | Oct 09/2008 |
| O | 10 | Oct 09/2008 | O | 5 | Oct 09/2008 | O | 11 | Oct 09/2008 |
| O | 11 | Oct 09/2008 | O | 6 | Oct 09/2008 | O | 12 | Oct 09/2008 |
| O | 12 | Oct 09/2008 | O | 7 | Oct 09/2008 | O | 13 | Oct 09/2008 |
| O | 13 | Oct 09/2008 | O | 8 | Oct 09/2008 | O | 14 | Oct 09/2008 |
| O | 14 | Oct 09/2008 | O | 9 | Oct 09/2008 | O | 15 | Oct 09/2008 |
| O | 15 | Oct 09/2008 | O | 10 | Oct 09/2008 | O | 16 | Oct 09/2008 |
| O W4160 | 1 | Oct 09/2008 | O | 11 | Oct 09/2008 | O | 17 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | O | 12 | Oct 09/2008 | O | 18 | Oct 09/2008 |
| O W4200 | 1 | Oct 09/2008 | O | 13 | Oct 09/2008 | O | 19 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | O | 14 | Oct 09/2008 | O | 20 | Oct 09/2008 |
| O | 3 | Oct 09/2008 | O | 15 | Oct 09/2008 | O | 21 | Oct 09/2008 |
| R | 4 | Oct 09/2008 | O | 16 | Oct 09/2008 | O | 22 | Oct 09/2008 |
| O | 5 | Oct 09/2008 | O | 17 | Oct 09/2008 | O W4230 | 1 | Oct 09/2008 |
| R | 6 | Oct 09/2008 | R | 18 | Oct 09/2008 | O | 2 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 19
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

91-21-11 WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W4230 cont. | | | W4420 cont. | | | W4470 cont. | | |
| O | 3 | Oct 09/2008 | O | 5 | Oct 09/2008 | O | 17 | Oct 09/2008 |
| O | 4 | Oct 09/2008 | O | 6 | Oct 09/2008 | O | 18 | Oct 09/2008 |
| O | 5 | Oct 09/2008 | O | 7 | Oct 09/2008 | O | 19 | Oct 09/2008 |
| O | 6 | Oct 09/2008 | O | 8 | Oct 09/2008 | O | 20 | Oct 09/2008 |
| O | 7 | Oct 09/2008 | O | 9 | Oct 09/2008 | O | 21 | Oct 09/2008 |
| O | 8 | Oct 09/2008 | O W4440 | 1 | Oct 09/2008 | O | 22 | Oct 09/2008 |
| O | 9 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 23 | Oct 09/2008 |
| O | 10 | Oct 09/2008 | O | 3 | Oct 09/2008 | O | 24 | Oct 09/2008 |
| O | 11 | Oct 09/2008 | O | 4 | Oct 09/2008 | O | 25 | Oct 09/2008 |
| O | 12 | Oct 09/2008 | O W4450 | 1 | Oct 09/2008 | O | 26 | Oct 09/2008 |
| O | 13 | Oct 09/2008 | O W4460 | 1 | Oct 09/2008 | O | 27 | Oct 09/2008 |
| O | 14 | Oct 09/2008 | O W4470 | 1 | Oct 09/2008 | O | 28 | Oct 09/2008 |
| O | 15 | Oct 09/2008 | O | 2 | Oct 09/2008 | O | 29 | Oct 09/2008 |
| O | 16 | Oct 09/2008 | O | 3 | Oct 09/2008 | O | 30 | Oct 09/2008 |
| O | 17 | Oct 09/2008 | O | 4 | Oct 09/2008 | O | 31 | Oct 09/2008 |
| O | 18 | Oct 09/2008 | O | 5 | Oct 09/2008 | O | 32 | Oct 09/2008 |
| O | 19 | Oct 09/2008 | O | 6 | Oct 09/2008 | O | 33 | Oct 09/2008 |
| O | 20 | Oct 09/2008 | O | 7 | Oct 09/2008 | O | 34 | Oct 09/2008 |
| O | 21 | Oct 09/2008 | O | 8 | Oct 09/2008 | O | 35 | Oct 09/2008 |
| O W4300 | 1 | Oct 09/2008 | O | 9 | Oct 09/2008 | O | 36 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | O | 10 | Oct 09/2008 | O | 37 | Oct 09/2008 |
| O W4310 | 1 | Oct 09/2008 | O | 11 | Oct 09/2008 | O | 38 | Oct 09/2008 |
| O W4400 | 1 | Oct 09/2008 | O | 12 | Oct 09/2008 | O | 39 | Oct 09/2008 |
| O W4420 | 1 | Oct 09/2008 | O | 13 | Oct 09/2008 | O | 40 | Oct 09/2008 |
| O | 2 | Oct 09/2008 | O | 14 | Oct 09/2008 | O | 41 | Oct 09/2008 |
| O | 3 | Oct 09/2008 | O | 15 | Oct 09/2008 | O | 42 | Oct 09/2008 |
| O | 4 | Oct 09/2008 | O | 16 | Oct 09/2008 | R | 43 | Oct 09/2008 |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 20
Oct 09/2008

91-21-11
WIRE LIST

| Section | Page | Date | Section | Page | Date | Section | Page | Date |
|-------------|------|-------------|-------------|------|-------------|-------------|------|-------------|
| W4470 cont. | | | W4480 cont. | | | W5200 cont. | | |
| O | 44 | Oct 09/2008 | R | 6 | Oct 09/2008 | | 2 | May 17/2006 |
| O | 45 | Oct 09/2008 | W4500 | 1 | May 17/2006 | | 3 | May 17/2006 |
| O | 46 | Oct 09/2008 | | 2 | May 17/2006 | | 4 | May 17/2006 |
| R | 47 | Oct 09/2008 | | 3 | May 17/2006 | | 5 | May 17/2006 |
| O | 48 | Oct 09/2008 | | 4 | May 17/2006 | | 6 | May 17/2006 |
| O | 49 | Oct 09/2008 | | 5 | May 17/2006 | | 7 | May 17/2006 |
| O | 50 | Oct 09/2008 | | 6 | May 17/2006 | W5210 | 1 | May 17/2006 |
| R | 51 | Oct 09/2008 | | 7 | May 17/2006 | | | |
| O | 52 | Oct 09/2008 | | 8 | May 17/2006 | | | |
| O | 53 | Oct 09/2008 | | 9 | May 17/2006 | | | |
| O | 54 | Oct 09/2008 | W4510 | 1 | May 17/2006 | | | |
| O | 55 | Oct 09/2008 | | 2 | May 17/2006 | | | |
| R | 56 | Oct 09/2008 | W4600 | 1 | May 17/2006 | | | |
| O | 57 | Oct 09/2008 | W4900 | 1 | May 17/2006 | | | |
| O | 58 | Oct 09/2008 | W4910 | 1 | May 17/2006 | | | |
| O | 59 | Oct 09/2008 | W4920 | 1 | May 17/2006 | | | |
| O | 60 | Oct 09/2008 | W4930 | 1 | May 17/2006 | | | |
| R | 61 | Oct 09/2008 | W5100 | 1 | May 17/2006 | | | |
| R | 62 | Oct 09/2008 | | 2 | May 17/2006 | | | |
| O | 63 | Oct 09/2008 | | 3 | May 17/2006 | | | |
| R | 64 | Oct 09/2008 | | 4 | May 17/2006 | | | |
| A | 65 | Oct 09/2008 | | 5 | May 17/2006 | | | |
| R W4480 | 1 | Oct 09/2008 | | 6 | May 17/2006 | | | |
| R | 2 | Oct 09/2008 | | 7 | May 17/2006 | | | |
| R | 3 | Oct 09/2008 | | 8 | May 17/2006 | | | |
| R | 4 | Oct 09/2008 | W5110 | 1 | May 17/2006 | | | |
| R | 5 | Oct 09/2008 | W5200 | 1 | May 17/2006 | | | |

A = Added, R = Revised, D = Deleted, O = Overflow

WIRE LIST

D280N032

EFFECTIVE PAGES

Page 21
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE | | | | | | | | | | | |
| 0001 | 22 | GA | | | 7-2 | 34-46-11 | D40427P | | | | D40523P | 19 | | | ALL |
| 0002 | 24 | GK | | | 5-0 | 34-21-11 | D40031P | | | | TB0014Y | A011 | BJ | | ALL |
| 0003 | 22 | GA | | | 10-6 | 33-16-11 | D41834P | | | | D40209P | 16 | | | ALL |
| 0004 | 20 | GA | | | 8-1 | 33-16-11 | D40209P | | | | GD01011 | DC.. | 2 | | ALL |
| 0005 | 22 | GA | | | 10-6 | 33-16-11 | D41834P | | | | D40209P | 12 | | | ALL |
| 0006 | 22 | GA | | | 15-8 | 33-16-11 | D41834P | | | | TB0013Y | C007 | BJ | | ALL |
| 0007 | 24 | GK | | | 7-2 | 34-12-12 | D40209P | | | | D40523P | 24 | | | ALL |
| 0008 | 22 | GA | | | 15-8 | 33-16-11 | D41834P | | | | TB0013Y | C014 | BJ | | ALL |
| 0009 | 22 | GA | | | 9-10 | 33-16-11 | D00279 | | | | TB0013Y | C014 | BJ | | ALL |
| 0010 | 22 | GA | | | 8-11 | 33-16-11 | D40209P | | | | TB0013Y | C014 | BJ | | ALL |
| 0011 | 22 | GA | | | 7-2 | 34-46-11 | D40209P | | | | D40523P | 18 | | | ALL |
| 0012 | 20 | GA | | | 8-11 | 34-24-11 | D00275 | | | | GD01015 | ST.. | 2 | | ALL |
| 0013 | 22 | GA | | | 7-2 | 34-61-15 | D40427P | | | | D40523P | 13 | | | ALL |
| 0014 | 24 | GK | | | 5-0 | 34-22-37 | D42047P | | | | TB0013X | A001 | BJ | | ALL |
| 0015 | 22 | GA | | | 7-2 | 22-34-11 | D40427P | | | | D40523P | 15 | | | ALL |
| 0016 | 24 | GK | | | 5-3 | 34-22-16 | D40754P | | | | TB0014X | A002 | BJ | | ALL |
| 0017 | 24 | GK | | | 5-3 | 34-22-16 | D40754P | | | | TB0014X | D002 | BJ | | ALL |
| 0019 | 24 | GK | | | 7-2 | 34-46-11 | D40427P | | | | D40523P | 12 | | | ALL |
| 0020 | 20 | GA | | | 2-0 | 34-22-81 | D40077P | | | AA | GD01020 | ST.. | 2 | | 001-099 |
| 0020 | 20 | GA | | | 2-0 | 34-22-83 | D40077P | | | AA | GD01020 | ST.. | 2 | | 115-199 |
| 0021 | 22 | GA | | | 5-0 | 34-12-61 | D40031P | | | | TB0014Y | A011 | BJ | | ALL |
| 0022 | 22 | GA | | | 7-2 | 34-46-11 | D40427P | | | | D40523P | 17 | | | ALL |
| 0023 | 22 | GA | | | 8-5 | 22-14-11 | D00401 | | | | D42047P | 18 | | | ALL |
| 0024 | 20 | GA | | | 8-3 | 33-13-12 | D40427P | | | | GD01016 | ST.. | 2 | | ALL |
| 0025 | 22 | GA | | | 8-1 | 30-43-11 | D01748 | | | | D41846P | 10 | | | ALL |
| 0026 | 22 | GA | | | 7-2 | 34-16-11 | D40427P | | | | D40523P | 26 | | | ALL |
| 0027 | 20 | GA | | | 9-1 | 30-43-11 | D01748 | | | | GD01015 | DC.. | 2 | | ALL |
| 0028 | 22 | GA | | | 7-0 | 22-14-11 | D40427P | | | | D40077P | 49 | | | ALL |
| 0029 | 22 | GA | | | 7-0 | 22-14-11 | D40427P | | | | D40077P | 50 | | | ALL |
| 0030 | 22 | GA | | | 7-5 | 22-14-11 | D40209P | | | | D42047P | 6 | | | ALL |
| 0031 | 22 | GA | | | 8-5 | 22-14-11 | D00401 | | | | D42047P | 19 | | | ALL |
| 0032 | 22 | GA | | | 5-1 | 31-41-11 | D40754P | | | | TB0013X | A029 | BJ | | ALL |
| 0033 | 22 | GA | | | 7-8 | 22-14-11 | D00485 | | | | D40039P | 3 | | | ALL |
| 0034 | 22 | GA | | | 7-8 | 22-14-11 | D00485 | | | | D40039P | 4 | | | ALL |
| 0035 | 22 | GA | | | 7-8 | 22-14-11 | D00485 | | | | D40039P | 5 | | | ALL |
| 0036 | 22 | GA | | | 8-2 | 22-14-11 | D00485 | | | | D40031P | 6 | | | ALL |
| 0037 | 20 | GA | | | 8-11 | 22-14-11 | D00401 | | | | GD01010 | ST.. | 2 | | ALL |
| 0038 | 20 | GA | | | 2-0 | 34-22-82 | D42047P | | | AH | GD01020 | ST.. | 2 | | ALL |
| 0039 | 20 | GA | | | 8-11 | 22-14-11 | D00485 | | | | GD01010 | DC.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0040 | 20 | | GA | | 8-11 | 22-14-11 | D00485 | | 12 | | GD01010 | ST.. | 2 | | ALL | |
| 0041 | 24 | | GK | | 14-1 | 34-21-31 | D42047P | | 1 | | TB0016X | C009 | BJ | | ALL | |
| 0042 | 24 | | GK | | 7-2 | 26-11-11 | D40209P | | 3 | | D40523P | | 53 | | ALL | |
| 0043 | 22 | | GA | | 8-11 | 34-32-11 | D40209P | | 13 | | TB0013Y | A004 | BJ | | ALL | |
| 0044 | 22 | | GA | | 8-11 | 34-32-11 | D40209P | | 14 | | TB0013Y | C003 | BJ | | ALL | |
| 0045 | 22 | | GA | | 8-11 | 34-32-11 | D40209P | | 15 | | TB0013Y | A003 | BJ | | ALL | |
| 0046 | 20 | | GA | | 9-1 | 30-43-11 | D01748 | | 2 | | GD01015 | ST.. | 2 | | ALL | |
| 0047 | 22 | | GA | | 4-10 | 34-32-11 | D40031P | | 47 | | TB0013Y | A003 | BJ | | ALL | |
| 0048 | 22 | | GA | | 4-10 | 34-32-11 | D40031P | | 48 | | TB0013Y | C003 | BJ | | ALL | |
| 0049 | 22 | | GA | | 4-10 | 34-32-11 | D40031P | | 49 | | TB0013Y | A004 | BJ | | ALL | |
| 0052 | 22 | | GA | | 10-6 | 33-16-21 | D40209P | | 20 | | D41834P | | 12 | | ALL | |
| 0053 | 22 | | GA | | 7-0 | 32-42-12 | D40427P | | 9 | | D40077P | | 39 | | ALL | |
| 0054 | 22 | | GA | | 5-0 | 32-42-12 | D40523P | | 47 | | TB0014Z | | 7 | BJ | ALL | |
| 0055 | 22 | | GA | | 5-0 | 32-42-12 | D40523P | | 55 | | TB0014Z | | 8 | BJ | ALL | |
| 0057 | 22 | | GA | | 15-8 | 33-16-21 | D41834P | | 10 | | TB0013Y | C011 | BJ | | 115-199 | |
| 0058 | 22 | | GA | | 12-2 | 33-16-21 | D00279 | | 11 | | D41834P | | 10 | | 001-099 | |
| 0058 | 22 | | GA | | 9-10 | 33-16-21 | D00279 | | 11 | | TB0013Y | C011 | BJ | | 115-199 | |
| 0059 | 22 | | GA | | 15-8 | 33-16-21 | D41834P | | 13 | | TB0013Y | C008 | BJ | | ALL | |
| 0060 | 20 | | GA | | 2-0 | 31-25-11 | D40031P | | | AB | GD01020 | ST.. | 2 | | ALL | |
| 0061 | 22 | | GA | | 10-6 | 33-16-41 | D40427P | | 2 | | TB0015X | D022 | BJ | | ALL | |
| 0062 | 22 | | GA | | 10-6 | 33-16-41 | D40427P | | 1 | | TB0015Z | | 14 | BJ | ALL | |
| 0063 | 22 | | GA | | 15-8 | 33-16-11 | D41834P | | 4 | | TB0013Y | A007 | BJ | | ALL | |
| 0064 | 20 | | GA | | 0-10 | 77-12-31 | D40523P | | | AC | GD01018 | ST.. | 2 | | 001-099 | |
| 0064 | 20 | | GA | | 1-6 | 77-12-31 | D40523P | | | AF | GD01018 | ST.. | 2 | | 115-199 | |
| 0065 | 20 | | GA | | 0-10 | 77-12-31 | D40077P | | | AD | GD01018 | ST.. | 2 | | 001-099 | |
| 0065 | 20 | | GA | | 1-6 | 77-12-31 | D40077P | | | AG | GD01018 | ST.. | 2 | | 115-199 | |
| 0066 | 18 | | GA | | 8-11 | 30-42-11 | D41846P | | 21 | | D01750 | | 3 | | ALL | |
| 0067 | 16 | | GA | | 9-4 | 30-42-11 | D40754P | | 23 | | D01750 | | 1 | | ALL | |
| 0068 | 18 | | GA | | 8-11 | 30-42-11 | D41846P | | 23 | | D01750 | | 2 | | ALL | |
| 0070 | 16 | | GA | | 9-11 | 30-42-11 | D01750 | | 6 | | GD01015 | DC.. | 2 | | ALL | |
| 0071 | 18 | | GA | | 9-11 | 30-42-11 | D01750 | | 5 | | GD01015 | ST.. | 2 | | ALL | |
| 0074 | 24 | | GK | | 4-4 | 31-31-31 | D40039P | | 1 | | TB0013Y | A003 | BJ | | 115-199 | |
| 0075 | 24 | | GK | | 4-4 | 31-31-31 | D40039P | | 2 | | TB0013Y | C003 | BJ | | 115-199 | |
| 0076 | 24 | | GK | | 4-4 | 31-31-31 | D40039P | | 15 | | TB0013Y | A004 | BJ | | 115-199 | |
| 0077 | 22 | | GA | | 2-10 | 33-16-51 | D41878P | | 18 | | TB0015Y | C015 | BJ | | 001-099 | |
| 0077 | 22 | | GA | | 2-10 | 33-16-51 | TB0015Y | C015 | BJ | | D41878P | | 18 | | 115-199 | |
| 0079 | 20 | | GA | | 3-2 | 33-13-11 | D00183 | | 1 | | SM00016 | | | W | 001-099 | |
| 0080 | 24 | | GK | | 10-1 | 34-13-21 | D00279 | | 12 | | TB0014Y | A009 | BJ | | ALL | |
| 0081 | 20 | | GA | | 2-0 | 34-22-82 | D40031P | | | AJ | GD01020 | ST.. | 2 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 2

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0082 | 24 | | GK | | 5-0 | 34-13-21 | D40031P | 18 | | | TB0014Y | A009 | BJ | | ALL |
| 0083 | 20 | | GA | | 4-6 | 33-13-11 | D02192 | 11 | | | GD01011 | AC.. | 2 | | ALL |
| 0084 | 20 | | GA | | 4-6 | 33-13-11 | D02192 | 7 | | | GD01011 | ST.. | 2 | | ALL |
| 0085 | 20 | | GA | | 5-1 | 33-13-11 | SM00011 | | W | | GD01011 | AC.. | 2 | | ALL |
| 0086 | 20 | | GA | | 6-8 | 33-13-11 | D40671P | 23 | | | GD01011 | AC.. | 2 | | ALL |
| 0087 | 20 | | GA | | 7-2 | 33-13-11 | D00277 | 2 | | | GD01011 | AC.. | 2 | | ALL |
| 0088 | 20 | | GA | | 7-2 | 33-13-11 | D00183 | 2 | | | GD01011 | AC.. | 2 | | 001-099 |
| 0088 | 20 | | GA | | 5-3 | 33-13-12 | D00771 | 2 | | | SM00009 | | W | | 115-199 |
| 0089 | 20 | | GA | | 5-5 | 33-13-11 | D02884 | C2 | | | SM00016 | | W | | 001-099 |
| 0089 | 20 | | GA | | 5-5 | 33-13-12 | D02884 | C2 | | | SM00013 | | W | | 115-199 |
| 0090 | 20 | | GA | | 3-2 | 33-13-11 | D00277 | 1 | | | SM00015 | | W | | ALL |
| 0091 | 20 | | GA | | 2-8 | 33-13-11 | D40671P | 22 | | | SM00015 | | W | | ALL |
| 0092 | 20 | | GA | | 5-5 | 33-13-11 | D02884 | C1 | | | SM00015 | | W | | ALL |
| 0093 | 20 | | GA | | 4-10 | 33-13-11 | D02192 | 8 | | | SM00015 | | W | | ALL |
| 0094 | 20 | | GA | | 4-10 | 33-13-11 | D02192 | 9 | | | SM00003 | | W | | ALL |
| 0095 | 20 | | GA | | 4-10 | 33-13-11 | D02192 | 2 | | | SM00014 | | W | | ALL |
| 0096 | 20 | | GA | | 7-11 | 31-41-19 | D40209P | 22 | | | GD01010 | ST.. | 2 | | ALL |
| 0097 | 20 | | GA | | 7-11 | 31-41-19 | D40209P | 23 | | | GD01010 | ST.. | 2 | | ALL |
| 0098 | 24 | | GK | | 4-5 | 33-13-11 | D40754P | 14 | | | SM00010 | | W | | ALL |
| 0101 | 22 | | GA | | 8-5 | 32-42-12 | D02374 | 1 | | | D41846P | 9 | | | 001-099 |
| 0101 | 20 | | GA | | 12-8 | 32-42-12 | D02374 | 1 | | | TB0016X | D002 | BJ | | 115-199 |
| 0102 | 20 | | GA | | 5-1 | 33-13-11 | D00485 | 3 | | | SM00003 | | W | | ALL |
| 0103 | 20 | | GA | | 5-1 | 33-13-11 | D00485 | 13 | | | SM00011 | | W | | ALL |
| 0104 | 20 | | GA | | 5-0 | 33-13-11 | D00279 | 1 | | | SM00003 | | W | | ALL |
| 0105 | 20 | | GA | | 5-0 | 33-13-11 | D00279 | 2 | | | SM00011 | | W | | ALL |
| 0106 | 20 | | GA | | 4-11 | 33-13-11 | D00187 | 1 | | | SM00003 | | W | | ALL |
| 0107 | 20 | | GA | | 4-11 | 33-13-11 | D00187 | 2 | | | SM00011 | | W | | ALL |
| 0108 | 20 | | GA | | 5-3 | 33-13-11 | D00463 | 1 | | | SM00016 | | W | | 001-099 |
| 0108 | 20 | | GA | | 3-5 | 33-13-11 | D00463 | 1 | | | SM00013 | | W | | 115-199 |
| 0109 | 20 | | GA | | 5-3 | 33-13-11 | D00463 | 2 | | | SM00011 | | W | | 001-099 |
| 0109 | 20 | | GA | | 3-5 | 33-13-11 | D00463 | 2 | | | SM00011 | | W | | 115-199 |
| 0110 | 22 | | GA | | 5-0 | 34-16-11 | D40523P | 10 | | | TB0014Y | A011 | BJ | | ALL |
| 0111 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | 11 | | | TB0014Z | 7 | BJ | | ALL |
| 0112 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | 12 | | | TB0014Z | 7 | BJ | | ALL |
| 0113 | 24 | | GK | | 10-6 | 21-33-12 | D40209P | 4 | | | D41834P | 3 | | | ALL |
| 0114 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | 14 | | | TB0014Z | 8 | BJ | | ALL |
| 0115 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | 15 | | | TB0014Z | 8 | BJ | | ALL |
| 0116 | 22 | | GA | | 8-8 | 32-42-12 | D02374 | 16 | | | D40523P | 34 | | | ALL |
| 0117 | 22 | | GA | | 9-3 | 32-42-12 | D02374 | 17 | | | GD01014 | DC.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 3

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0118 | 22 | | GA | | 9-3 | 32-42-12 | D02374 | | | | GD01014 | DC.. | 2 | | ALL | |
| 0119 | 20 | | GA | | 5-1 | 33-13-12 | D00275 | | | 1 | SM00007 | | W | | ALL | |
| 0120 | 20 | | GA | | 5-1 | 33-13-12 | D00275 | | | 2 | SM00009 | | W | | ALL | |
| 0121 | 20 | | GA | | 5-4 | 33-13-12 | D00283 | | | 1 | SM00007 | | W | | ALL | |
| 0122 | 20 | | GA | | 5-4 | 33-13-12 | D00283 | | | 2 | SM00009 | | W | | ALL | |
| 0123 | 22 | | GA | | 6-1 | 32-42-12 | D02374 | | | 23 | SM00017 | | W | | ALL | |
| 0124 | 22 | | GA | | 9-3 | 32-42-12 | D02374 | | | 24 | GD01014 | DC.. | 2 | | ALL | |
| 0125 | 22 | | GA | | 7-2 | 79-33-11 | D40209P | | | 19 | D40523P | 54 | | | ALL | |
| 0126 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | | | 26 | TB0014Z | 7 | BJ | | ALL | |
| 0127 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | | | 27 | TB0014Z | 7 | BJ | | ALL | |
| 0128 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | | | 28 | TB0014Z | 7 | BJ | | ALL | |
| 0129 | 22 | | GA | | 8-8 | 32-42-12 | D02374 | | | 19 | D40523P | 37 | | | ALL | |
| 0130 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | | | 30 | TB0014Z | 8 | BJ | | ALL | |
| 0131 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | | | 31 | TB0014Z | 8 | BJ | | ALL | |
| 0132 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | | | 32 | TB0014Z | 8 | BJ | | ALL | |
| 0133 | 22 | | GA | | 5-5 | 32-42-12 | D40427P | | | 11 | D02374 | 33 | | | ALL | |
| 0134 | 22 | | GA | | 9-3 | 32-42-12 | D02374 | | | 34 | GD01014 | DC.. | 2 | | ALL | |
| 0135 | 22 | | GA | | 10-7 | 32-42-12 | D02374 | | | 35 | TB0014Z | 8 | BJ | | ALL | |
| 0136 | 22 | | GA | | 7-0 | 79-33-11 | D40427P | | | 10 | D40077P | 38 | | | ALL | |
| 0137 | 22 | | GA | | 8-8 | 32-42-12 | D02374 | | | 37 | D40523P | 52 | | | ALL | |
| 0138 | 22 | | GA | | 8-8 | 32-42-12 | D02374 | | | 38 | D40523P | 49 | | | ALL | |
| 0139 | 22 | | GA | | 8-8 | 32-42-12 | D02374 | | | 39 | D40523P | 50 | | | ALL | |
| 0140 | 22 | | GA | | 8-8 | 32-42-12 | D02374 | | | 40 | D40523P | 51 | | | ALL | |
| 0141 | 22 | | GA | | 8-8 | 32-42-12 | D02374 | | | 41 | D40523P | 35 | | | ALL | |
| 0142 | 20 | | GA | | 5-3 | 33-13-12 | SM00013 | | W | | D00771 | 1 | | | 115-199 | |
| 0143 | 20 | | GA | | 6-0 | 33-13-12 | D00281 | | | 1 | SM00007 | | W | | ALL | |
| 0144 | 20 | | GA | | 6-0 | 33-13-12 | D00281 | | | 2 | SM00009 | | W | | ALL | |
| 0145 | 20 | | GA | | 5-4 | 33-13-12 | D02208 | | | 1 | SM00007 | | W | | ALL | |
| 0146 | 20 | | GA | | 5-4 | 33-13-12 | D02208 | | | 2 | SM00009 | | W | | ALL | |
| 0147 | 20 | | GA | | 4-9 | 33-13-12 | SM00009 | | W | | GD01009 | AC.. | 2 | | ALL | |
| 0148 | 20 | | GA | | 7-10 | 33-13-12 | D40209P | | | 30 | GD01009 | AC.. | 2 | | ALL | |
| 0149 | 20 | | GA | | 3-1 | 33-13-12 | D40209P | | | 29 | SP00207 | | W | | 001-099 | |
| 0149 | 20 | | GA | | 3-1 | 33-13-12 | SP00207 | | W | | D40209P | 29 | | | 115-199 | |
| 0150 | 20 | | GA | | 7-9 | 33-13-12 | D40427P | | | 8 | GD01009 | AC.. | 2 | | ALL | |
| 0151 | 20 | | GA | | 3-0 | 33-13-12 | D40427P | | | 7 | SP00207 | | W | | ALL | |
| 0152 | 24 | | GK | | 1-7 | 33-13-12 | D02884 | | D2 | | D02914 | 12 | | | ALL | |
| 0153 | 24 | | GK | | 7-2 | 31-51-43 | D40209P | | | 34 | D40523P | 14 | | | ALL | |
| 0154 | 20 | | GA | | 3-9 | 33-13-12 | D02884 | | B1 | | SP00207 | | W | | ALL | |
| 0155 | 20 | | GA | | 1-7 | 33-13-12 | D02884 | | B2 | | D02914 | 9 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 4

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| | 0158 | 20 | GA | | 4-4 | 33-13-12 | SM00008 | | W | | SM00007 | | W | | ALL |
| | 0159 | 20 | GA | | 4-4 | 33-13-11 | D40758P | 9 | | | SM00014 | | W | | ALL |
| | 0160 | 20 | GA | | 8-6 | 33-13-12 | D02914 | 2 | | | SM00008 | | W | | ALL |
| I | 0161 | 22 | GA | | 11-6 | 34-61-25 | D40281P | 3 | | | TB0015X | D021 | BJ | | 001-099 |
| I | 0162 | 22 | GA | | 5-2 | 34-61-25 | D40281P | 4 | | | D40077P | 52 | | | 001-099 |
| | 0163 | 22 | GA | | 5-0 | 34-12-62 | D40758P | 6 | | | TB0013X | A020 | BJ | | ALL |
| | 0164 | 20 | GA | | 9-2 | 33-13-12 | D02884 | X2 | | | GD01009 | AC.. | 2 | | ALL |
| | 0165 | 24 | GK | | 5-5 | 33-13-12 | D02884 | X1 | | | SM00010 | | W | | ALL |
| | 0167 | 20 | GA | | 8-8 | 33-13-12 | D02884 | C3 | | | SM00008 | | W | | ALL |
| | 0168 | 24 | GK | | 5-5 | 33-13-12 | D02884 | D1 | | | SM00010 | | W | | ALL |
| | 0169 | 20 | GA | | 9-5 | 33-13-12 | D02914 | 7 | | | GD01016 | ST.. | 2 | | ALL |
| | 0170 | 24 | GK | | 4-10 | 33-13-11 | D02192 | 12 | | | SM00010 | | W | | ALL |
| | 0171 | 16 | GA | | 9-5 | 33-13-12 | D02914 | 11 | 16 | | GD01016 | AC.. | 2 | | ALL |
| | 0172 | 22 | GA | | 8-6 | 31-25-11 | D40758P | 10 | | | D00463 | 3 | | | 001-099 |
| | 0172 | 22 | GA | | 6-8 | 31-25-11 | D40758P | 10 | | | D00463 | 3 | | | 115-199 |
| | 0173 | 22 | GA | | 5-1 | 33-14-21 | D40754P | 1 | | | TB0013Y | A012 | BJ | | ALL |
| | 0174 | 22 | GA | | 11-3 | 33-14-21 | D40850P | 21 | | | TB0013Y | A012 | BJ | | ALL |
| I | 0175 | 22 | GA | | 6-0 | 34-61-15 | D40671P | 6 | | | D40754P | 22 | | | 001-099 |
| I | 0175 | 22 | GA | | 6-0 | 34-61-15 | D40671P | 6 | | | GD01019 | DC.. | 2 | | 115-199 |
| | 0176 | 22 | GA | | 4-9 | 34-61-15 | D40671P | 7 | | | D40039P | 36 | | | ALL |
| | 0177 | 24 | GK | | 10-2 | 77-12-11 | D02208 | 20 | | | TB0013X | B001 | BJ | | ALL |
| | 0178 | 24 | GK | | 10-2 | 77-12-11 | D02210 | 20 | | | TB0013X | A005 | BJ | | ALL |
| | 0181 | 20 | GA | | 6-8 | 22-41-13 | D40281P | 18 | | | GD01011 | DC.. | 2 | | ALL |
| | 0184 | 20 | GA | | 7-10 | 34-46-11 | D40427P | 20 | | | GD01010 | ST.. | 2 | | ALL |
| | 0185 | 22 | GA | | 5-2 | 22-41-13 | D40281P | 17 | | | D40077P | 23 | | | ALL |
| | 0186 | 22 | GA | | 5-4 | 22-41-13 | D40281P | 16 | | | D40031P | 1 | | | ALL |
| | 0187 | 22 | GA | | 5-4 | 22-41-13 | D40281P | 15 | | | D40031P | 11 | | | ALL |
| | 0188 | 24 | GK | | 11-6 | 34-22-15 | D40850P | 35 | | | TB0014X | A001 | BJ | | ALL |
| | 0189 | 24 | GK | | 11-6 | 34-22-15 | D40850P | 36 | | | TB0014X | B001 | BJ | | ALL |
| | 0190 | 24 | GK | | 11-6 | 34-22-15 | D40850P | 37 | | | TB0014X | C001 | BJ | | ALL |
| | 0191 | 20 | GA | | 6-8 | 34-22-16 | D40671P | 33 | | | GD01011 | ST.. | 2 | | ALL |
| | 0192 | 22 | GA | | 5-3 | 34-22-16 | D40671P | 32 | | | D40031P | 10 | | | ALL |
| | 0193 | 24 | GK | | 7-8 | 34-22-17 | D40671P | 9 | | | TB0014Y | C009 | BJ | | ALL |
| | 0194 | 24 | GK | | 5-3 | 34-22-17 | D40671P | 17 | | | D40031P | 17 | | | ALL |
| | 0195 | 24 | GK | | 5-3 | 34-22-17 | D40671P | 11 | | | D40031P | 19 | | | ALL |
| | 0196 | 24 | GK | | 5-3 | 34-22-17 | D40671P | 13 | | | D40031P | 15 | | | ALL |
| | 0197 | 24 | GK | | 5-3 | 34-22-17 | D40671P | 14 | | | D40031P | 16 | | | ALL |
| | 0198 | 22 | GA | | 5-3 | 34-22-17 | D40671P | 16 | | | D40031P | 20 | | | ALL |
| | 0199 | 24 | GK | | 5-0 | 34-22-17 | D40031P | 13 | | | TB0014Y | C009 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0201 | 20 | | GA | | 10-8 | 31-51-21 | D40850P | 28 | | | GD01016 | DC.. | 2 | | ALL |
| 0202 | 22 | | GA | | 4-4 | 31-51-21 | D40039P | 31 | | | TB0013Y | C004 | BJ | | ALL |
| 0203 | 22 | | GA | | 11-3 | 31-51-21 | D40850P | 26 | | | TB0013Y | C004 | BJ | | ALL |
| 0204 | 22 | | GA | | 9-1 | 31-51-21 | D40850P | 27 | | | D40039P | 32 | | | ALL |
| 0205 | 20 | | GA | | 4-9 | 33-13-41 | D40850P | 1 | | | SP00215 | | W | | 001-099 |
| 0205 | 20 | | GA | | 4-9 | 33-13-41 | SP00215 | | W | | D40850P | 1 | | | 115-199 |
| 0206 | 20 | | GA | | 10-8 | 33-13-41 | D40850P | 2 | | | GD01016 | AC.. | 2 | | ALL |
| 0207 | 22 | | GA | | 15-8 | 33-16-11 | D41834P | 22 | | | TB0013X | A030 | BJ | | ALL |
| 0208 | 22 | | GA | | 15-8 | 33-16-11 | D41834P | 23 | | | TB0013X | B030 | BJ | | ALL |
| 0209 | 22 | | GA | | 15-8 | 33-16-11 | D41834P | 24 | | | TB0013X | D029 | BJ | | 001-099 |
| 0209 | 22 | | GA | | 15-8 | 33-16-11 | D41834P | 24 | | | TB0013X | C030 | BJ | | 115-199 |
| 0212 | 24 | | GK | | 6-0 | 34-22-37 | D40281P | 12 | | | D42047P | 23 | | | ALL |
| 0213 | 24 | | GK | | 11-6 | 34-22-37 | D40281P | 13 | | | TB0016Y | C008 | BJ | | ALL |
| 0214 | 24 | | GK | | 11-6 | 34-22-37 | D40281P | 5 | | | TB0016X | C010 | BJ | | ALL |
| 0215 | 22 | | GA | | 5-0 | 31-51-42 | D40031P | 14 | | | TB0014Y | A010 | BJ | | ALL |
| 0216 | 22 | | GA | | 9-2 | 31-51-42 | D40209P | 2 | | | TB0014Y | A010 | BJ | | ALL |
| 0217 | 22 | | GA | | 9-2 | 31-51-42 | D40209P | 1 | | | TB0014Y | A010 | BJ | | ALL |
| 0219 | 20 | | GA | | 6-6 | 34-22-37 | D40281P | 6 | | | GD01010 | DC.. | 2 | | ALL |
| 0221 | 20 | | GA | | 6-10 | 34-12-61 | D40671P | 27 | | | GD01012 | DC.. | 2 | | ALL |
| 0222 | 20 | | GA | | 6-10 | 34-12-61 | D40671P | 25 | | | D40758P | 5 | | | ALL |
| 0223 | 20 | | GA | | 6-10 | 34-12-61 | D40671P | 24 | | | GD01012 | DC.. | 2 | | ALL |
| 0224 | 20 | | GA | | 6-10 | 34-12-61 | D40671P | 26 | | | GD01012 | DC.. | 2 | | ALL |
| 0225 | 24 | | GK | | 6-6 | 34-13-11 | D40754P | 7 | | | D00277 | 3 | | | ALL |
| 0226 | 20 | | GA | | 7-0 | 34-13-11 | D00277 | 4 | | | GD01010 | AC.. | 2 | | ALL |
| 0227 | 20 | | GA | | 7-0 | 34-13-11 | D00277 | 7 | | | GD01010 | ST.. | 2 | | ALL |
| 0228 | 20 | | GA | | 7-0 | 34-13-11 | D00277 | 10 | | | GD01010 | DC.. | 2 | | ALL |
| 0229 | 24 | | GK | | 8-4 | 34-13-11 | D40754P | 8 | | | D00279 | 3 | | | ALL |
| 0230 | 20 | | GA | | 9-2 | 34-13-11 | D00279 | 4 | | | GD01012 | AC.. | 2 | | ALL |
| 0231 | 20 | | GA | | 9-2 | 34-13-11 | D00279 | 10 | | | GD01012 | DC.. | 2 | | ALL |
| 0232 | 20 | | GA | | 9-2 | 34-13-11 | D00279 | 7 | | | GD01012 | ST.. | 2 | | ALL |
| 0234 | 20 | | GA | | 9-9 | 34-13-11 | D00281 | 4 | | | GD01012 | DC.. | 2 | | ALL |
| 0237 | 20 | | GA | | 9-9 | 34-13-11 | D00281 | 5 | | | GD01012 | ST.. | 2 | | ALL |
| 0239 | 20 | | GA | | 9-6 | 34-13-11 | D00283 | 5 | | | GD01012 | ST.. | 2 | | ALL |
| 0241 | 22 | | GA | | 5-3 | 34-12-61 | D40671P | 29 | | | D40031P | 21 | | | ALL |
| 0242 | 22 | | GA | | 7-8 | 34-12-61 | D40671P | 30 | | | TB0014Y | A011 | BJ | | ALL |
| 0244 | 24 | | GK | | 9-2 | 31-41-19 | D40209P | 24 | | | TB0014X | C005 | BJ | | ALL |
| 0245 | 24 | | GK | | 9-2 | 31-41-19 | D40209P | 25 | | | TB0014X | D005 | BJ | | ALL |
| 0248 | 24 | | GK | | 5-4 | 33-11-11 | D00898 | 16 | | | SM00002 | | W | | ALL |
| 0249 | 24 | | GK | | 11-0 | 33-11-11 | D41878P | 2 | | | SM00002 | | W | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0250 | 20 | GA | | | 9-7 | 33-11-11 | D00898 | | 17 | | GD01016 | AC.. | 2 | | ALL |
| 0251 | 20 | GA | | | 9-7 | 33-11-11 | D00898 | | 21 | | GD01016 | ST.. | 2 | | ALL |
| 0252 | 20 | GA | | | 10-8 | 33-11-11 | D40850P | | 10 | | GD01016 | ST.. | 2 | | ALL |
| 0253 | 20 | GA | | | 9-10 | 33-11-11 | D00890 | | 5 | | GD01016 | ST.. | 2 | | ALL |
| 0273 | 22 | GA | | | 4-9 | 32-42-11 | D40671P | | 37 | | D40039P | | 34 | | ALL |
| 0274 | 20 | GA | | | 6-11 | 32-42-11 | D40671P | | 38 | | GD01020 | DC.. | 2 | | 001-099 |
| 0274 | 22 | GA | | | 6-11 | 32-42-11 | D40671P | | 38 | | GD01020 | DC.. | 2 | | 115-199 |
| 0275 | 22 | GA | | | 6-0 | 34-12-61 | D40671P | | 35 | | D40523P | | 29 | | ALL |
| 0276 | 22 | GA | | | 6-0 | 34-12-61 | D40671P | | 36 | | D40523P | | 41 | | 001-099 |
| 0276 | 22 | GA | | | 6-0 | 34-12-61 | D40671P | | 36 | | D40523P | | 30 | | 115-199 |
| 0292 | 20 | GA | | | 10-2 | 33-14-21 | D40850P | | 55 | | GD01009 | AC.. | 2 | | ALL |
| 0293 | 24 | GK | | | 6-2 | 33-13-11 | D05254 | | X1 | | SM00010 | | | W | 115-199 |
| 0294 | 20 | GA | | | 10-0 | 33-13-11 | D05254 | | X2 | | GD01020 | AC.. | 2 | | 115-199 |
| 0295 | 24 | GK | | | 4-10 | 33-13-11 | D02192 | | 1 | | SM00006 | | | W | 115-199 |
| 0301 | 24 | GK | | | 12-3 | 77-12-11 | D02208 | | 3 | | D41878P | | 12 | | ALL |
| 0302 | 24 | GK | | | 8-7 | 77-12-11 | D02210 | | 3 | | D40758P | | 4 | | ALL |
| 0303 | 24 | GK | | | 8-9 | 34-13-11 | D00281 | | 3 | | D40758P | | 2 | | ALL |
| 0304 | 24 | GK | | | 6-5 | 34-22-81 | D00183 | | 54 | | D40758P | | 1 | | 001-099 |
| 0304 | 24 | GK | | | 8-6 | 34-22-83 | D00771 | | 54 | | D40758P | | 1 | | 115-199 |
| 0305 | 20 | GA | | | 9-2 | 77-12-11 | D02208 | | 4 | | GD01010 | DC.. | 2 | | ALL |
| 0306 | 22 | GA | | | 12-2 | 31-25-11 | D41878P | | 27 | | D00463 | | 8 | | 001-099 |
| 0306 | 22 | GA | | | 12-10 | 31-25-11 | D41878P | | 27 | | D00463 | | 8 | | 115-199 |
| 0307 | 20 | GA | | | 9-1 | 77-12-11 | D02210 | | 4 | | GD01010 | DC.. | 2 | | ALL |
| 0308 | 20 | GA | | | 9-1 | 77-12-11 | D02210 | | 2 | | GD01010 | ST.. | 2 | | ALL |
| 0309 | 24 | GK | | | 12-7 | 34-22-83 | D00773 | | 1 | | TB0015X | A022 | BJ | | 115-199 |
| 0310 | 20 | GA | | | 4-9 | 33-11-21 | D40850P | | 16 | | SP00205 | | | W | ALL |
| 0311 | 20 | GA | | | 10-8 | 33-11-21 | D40850P | | 17 | | GD01012 | AC.. | 2 | | ALL |
| 0312 | 20 | GA | | | 9-4 | 34-22-83 | D00773 | | 2 | | GD01015 | DC.. | 2 | | 115-199 |
| 0316 | 24 | GK | | | 8-8 | 33-13-12 | D40758P | | 3 | | D02884 | | D3 | | ALL |
| 0318 | 20 | GA | | | 9-6 | 31-25-11 | D00463 | | 9 | | GD01012 | DC.. | 2 | | 001-099 |
| 0318 | 20 | GA | | | 7-7 | 31-25-11 | D00463 | | 9 | | GD01012 | DC.. | 2 | | 115-199 |
| 0319 | 22 | GA | | | 15-5 | 33-16-61 | D41878P | | 17 | | TB0013X | C015 | BJ | | ALL |
| 0320 | 22 | GA | | | 2-10 | 33-16-51 | D41878P | | 13 | | TB0015Y | A015 | BJ | | ALL |
| 0321 | 22 | GA | | | 2-10 | 33-16-51 | D41878P | | 14 | | TB0015Z | | 13 | BJ | ALL |
| 0322 | 22 | GA | | | 11-2 | 33-16-51 | D40850P | | 22 | | TB0015Y | A015 | BJ | | ALL |
| 0324 | 22 | GA | | | 11-2 | 33-16-51 | D40850P | | 24 | | TB0015Z | | 13 | BJ | ALL |
| 0326 | 22 | GA | | | 10-2 | 33-16-51 | D41878P | | 15 | | D40677P | | 4 | | ALL |
| 0327 | 22 | GA | | | 10-2 | 33-16-51 | D41878P | | 16 | | D40677P | | 3 | | ALL |
| 0328 | 22 | GA | | | 10-5 | 33-16-51 | TB0015Y | C015 | BJ | | D40677P | | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0329 | 22 | | GA | | 10-5 | 33-16-51 | D40677P | | | 1 | TB0015Z | 13 | BJ | | ALL |
| 0330 | 20 | | GA | | 7-9 | 33-16-51 | D40677P | | | 5 | GD01014 | DC.. | 2 | | ALL |
| 0332 | 22 | | GA | | 12-3 | 22-14-11 | D00401 | | | 1 | TB0016Y | C016 | BJ | | ALL |
| 0334 | 22 | | GA | | 10-5 | 33-16-61 | D40677P | | | 7 | TB0015Y | C024 | BJ | | ALL |
| 0335 | 24 | | GK | | 10-11 | 33-11-11 | D40850P | | | 41 | D41878P | 1 | | | ALL |
| 0337 | 24 | | GK | | 6-11 | 33-11-11 | D40850P | | | 42 | SM00002 | | W | | ALL |
| 0345 | 20 | | GA | | 7-0 | 34-22-81 | D00183 | | | 55 | GD01015 | AC.. | 2 | | 001-099 |
| 0345 | 20 | | GA | | 9-2 | 34-22-83 | D00771 | | | 55 | GD01015 | AC.. | 2 | | 115-199 |
| 0370 | 22 | | GA | | 10-5 | 33-16-51 | D40677P | | | 10 | TB0015Z | 3 | BJ | | ALL |
| 0371 | 24 | | GK | | 10-5 | 32-41-11 | D40677P | | | 9 | TB0015X | B022 | BJ | | ALL |
| 0372 | 22 | | GA | | 10-5 | 33-16-51 | D40677P | | | 8 | TB0015Z | 4 | BJ | | ALL |
| 0373 | 22 | | GA | | 2-10 | 33-16-51 | D41878P | | | 11 | TB0015Y | A017 | BJ | | 115-199 |
| 0401 | 24 | | GK | | 8-3 | 34-13-11 | D00277 | | | 8 | TB0014Y | C004 | BJ | | ALL |
| 0402 | 24 | | GK | | 7-8 | 34-13-11 | D40671P | | | 31 | TB0014Y | C004 | BJ | | ALL |
| 0403 | 24 | | GK | | 10-1 | 34-13-11 | D00279 | | | 8 | TB0014Y | C004 | BJ | | ALL |
| 0405 | 24 | | GK | | 12-10 | 34-22-81 | D00183 | | | 16 | TB0016Y | C007 | BJ | | 001-099 |
| 0405 | 24 | | GK | | 12-5 | 34-22-83 | D00771 | | | 16 | TB0016Y | C007 | BJ | | 115-199 |
| 0407 | 20 | | GA | | 7-0 | 34-22-81 | D00183 | | | 3 | GD01015 | DC.. | 2 | | 001-099 |
| 0407 | 20 | | GA | | 9-2 | 34-22-83 | D00771 | | | 3 | GD01015 | DC.. | 2 | | 115-199 |
| 0408 | 20 | | GA | | 7-0 | 34-22-81 | D00183 | | | 6 | GD01015 | ST.. | 2 | | 001-099 |
| 0408 | 20 | | GA | | 9-2 | 34-22-83 | D00771 | | | 6 | GD01015 | ST.. | 2 | | 115-199 |
| 0409 | 24 | | GK | | 12-10 | 34-22-81 | D00183 | | | 29 | TB0016Z | 11 | BJ | | 001-099 |
| 0410 | 24 | | GK | | 8-0 | 34-22-81 | D00183 | | | 21 | TB0013Z | 27 | BJ | | 001-099 |
| 0411 | 20 | | GA | | 7-0 | 34-22-81 | D00183 | | | 28 | GD01015 | ST.. | 2 | | 001-099 |
| 0412 | 22 | | GA | | 8-3 | 34-22-82 | D00187 | | | 3 | D40754P | 6 | | | 001-099 |
| 0412 | 24 | | GK | | 8-3 | 34-22-82 | D00187 | | | 3 | D40754P | 6 | | | 115-199 |
| 0413 | 20 | | GA | | 8-8 | 34-22-82 | D00187 | | | 4 | GD01014 | AC.. | 2 | | ALL |
| 0414 | 20 | | GA | | 8-8 | 34-22-82 | D00187 | | | 7 | GD01014 | ST.. | 2 | | ALL |
| 0415 | 20 | | GA | | 8-8 | 34-22-82 | D00187 | | | 10 | GD01014 | DC.. | 2 | | ALL |
| 0416 | 20 | | GA | | 6-4 | 34-22-82 | D40671P | | | 5 | GD01014 | DC.. | 2 | | ALL |
| 0417 | 24 | | GK | | 5-1 | 34-22-82 | D00187 | | | 8 | D40671P | 4 | | | ALL |
| 0418 | 20 | | GA | | 6-7 | 34-22-91 | D40281P | | | 14 | GD01015 | DC.. | 2 | | 001-099 |
| 0418 | 20 | | GA | | 6-7 | 34-22-93 | D40281P | | | 14 | GD01015 | DC.. | 2 | | 115-199 |
| 0419 | 24 | | GK | | 7-9 | 34-22-91 | D40281P | | | 1 | TB0014X | B002 | BJ | | 001-099 |
| 0419 | 24 | | GK | | 7-9 | 34-22-93 | D40281P | | | 1 | TB0014X | B002 | BJ | | 115-199 |
| 0421 | 20 | | GA | | 9-6 | 31-25-11 | D00463 | | | 7 | GD01012 | DC.. | 2 | | 001-099 |
| 0421 | 20 | | GA | | 7-7 | 31-25-11 | D00463 | | | 7 | GD01012 | DC.. | 2 | | 115-199 |
| 0424 | 20 | | GA | | 9-6 | 31-25-11 | D00463 | | | 4 | GD01012 | DC.. | 2 | | 001-099 |
| 0424 | 20 | | GA | | 7-7 | 31-25-11 | D00463 | | | 4 | GD01012 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0425 | 24 | GK | | | 11-2 | 33-14-11 | D40850P | | 18 | | TB0015Y | A016 | BJ | | ALL |
| 0426 | 22 | GA | | | 10-11 | 33-14-11 | D40850P | | 19 | | D41878P | 25 | | | 001-099 |
| 0426 | 22 | GA | | | 9-9 | 33-14-11 | D40850P | | 19 | | D40754P | 21 | | | 115-199 |
| 0429 | 20 | GA | | | 6-4 | 34-22-17 | D40671P | | 10 | | GD01014 | DC.. | 2 | | ALL |
| 0430 | 20 | GA | | | 6-4 | 34-22-17 | D40671P | | 12 | | GD01014 | DC.. | 2 | | ALL |
| 0431 | 20 | GA | | | 6-4 | 34-22-17 | D40671P | | 15 | | GD01014 | DC.. | 2 | | ALL |
| 0432 | 20 | GA | | | 6-4 | 34-22-17 | D40671P | | 21 | | GD01014 | DC.. | 2 | | ALL |
| 0433 | 24 | GK | | | 14-2 | 27-58-11 | D40754P | | 10 | | TB0016X | A021 | BJ | | 001-099 |
| 0433 | 22 | GA | | | 14-2 | 27-58-11 | D40754P | | 10 | | TB0016X | A021 | BJ | | 115-199 |
| 0434 | 24 | GK | | | 14-2 | 27-58-11 | D40754P | | 18 | | TB0016X | B021 | BJ | | 001-099 |
| 0434 | 22 | GA | | | 14-2 | 27-58-11 | D40754P | | 18 | | TB0016X | B021 | BJ | | 115-199 |
| 0435 | 22 | GA | | | 8-8 | 32-42-12 | D02374 | | 36 | | D40523P | 32 | | | 115-199 |
| 0436 | 22 | GA | | | 8-8 | 32-42-12 | D02374 | | 9 | | D40523P | 42 | | | 001-099 |
| 0436 | 22 | GA | | | 8-8 | 31-31-31 | D02374 | | 21 | | D40031P | 3 | | | 115-199 |
| 0437 | 22 | GA | | | 8-8 | 31-31-63 | D02374 | | 7 | | D40031P | 5 | | | 115-199 |
| 0438 | 22 | GA | | | 8-8 | 31-31-63 | D02374 | | 8 | | D40031P | 39 | | | 115-199 |
| 0440 | 22 | GA | | | 8-8 | 32-42-12 | D40523P | | 42 | | D02374 | 9 | | | 115-199 |
| 0442 | 22 | GA | | | 11-2 | 31-41-14 | D40850P | | 29 | | TB0015Y | C005 | BJ | | ALL |
| 0444 | 22 | GA | | | 8-8 | 31-31-63 | D02374 | | 4 | | D40031P | 4 | | | 115-199 |
| 0445 | 22 | GA | | | 8-8 | 31-31-63 | D02374 | | 5 | | D40031P | 40 | | | 115-199 |
| 0446 | 22 | GA | | | 8-8 | 31-31-63 | D02374 | | 6 | | D40031P | 38 | | | 115-199 |
| 0447 | 22 | GA | | | 8-8 | 31-31-63 | D02374 | | 3 | | D40031P | 31 | | | 115-199 |
| 0448 | 22 | GA | | | 11-2 | 31-41-14 | D40850P | | 48 | | TB0015Y | A005 | BJ | | ALL |
| 0449 | 20 | GA | | | 10-8 | 31-41-14 | D40850P | | 49 | | GD01016 | DC.. | 2 | | ALL |
| 0457 | 22 | GA | | | 0-7 | 22-14-11 | D00485 | | 15 | | D00485 | 4 | | | ALL |
| 0458 | 22 | GA | | | 5-1 | 22-14-11 | D00401 | | 9 | | SM00001 | | W | | ALL |
| 0459 | 22 | GA | | | 5-1 | 22-14-11 | D00401 | | 8 | | SM00001 | | W | | ALL |
| 0460 | 22 | GA | | | 5-1 | 22-14-11 | D00401 | | 2 | | SM00001 | | W | | ALL |
| 0461 | 22 | GA | | | 11-3 | 33-16-11 | D40850P | | 25 | | TB0013Y | C007 | BJ | | ALL |
| 0462 | 22 | GA | | | 11-3 | 33-16-21 | D40850P | | 23 | | TB0013Y | C008 | BJ | | ALL |
| 0464 | 20 | GA | | | 3-11 | 33-13-11 | D41846P | | 8 | | SM00014 | | W | | ALL |
| 0468 | 22 | PA | | | 6-6 | 34-61-18 | D40671P | | 28 | | GD01015 | DC.. | 2 | | 115-199 |
| 0469 | 22 | PA | | | 6-0 | 34-61-18 | D40671P | | 34 | | GD01015 | DC.. | 2 | | 115-199 |
| 0470 | 22 | PA | | | 4-9 | 34-61-18 | D40671P | | 39 | | D40039P | 26 | | | 115-199 |
| 0471 | 22 | PA | | | 6-6 | 34-61-18 | D40671P | | 40 | | GD01015 | DC.. | 2 | | 115-199 |
| 0472 | 22 | PA | | | 6-6 | 34-61-18 | D40671P | | 19 | | GD01015 | DC.. | 2 | | 115-199 |
| 0473 | 22 | PA | | | 5-1 | 34-61-18 | D40671P | | 20 | | D40077P | 11 | | | 115-199 |
| 0475 | 22 | GA | | | 8-8 | 32-42-12 | D02374 | | 36 | | D40523P | 32 | | | 001-099 |
| 0476 | 24 | GK | | | 8-4 | 34-24-11 | D00275 | | 18 | | D42047P | 50 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0477 | 24 | | GK | | 8-4 | 34-24-11 | D00275 | 15 | | | D42047P | 51 | | | ALL | |
| 0478 | 24 | | GK | | 8-4 | 34-24-11 | D00275 | 16 | | | D42047P | 52 | | | ALL | |
| 0479 | 24 | | GK | | 8-4 | 34-24-11 | D00275 | 17 | | | D42047P | 53 | | | ALL | |
| 0484 | 20 | | GA | | 3-7 | 33-13-41 | D02914 | 8 | | | SP00217 | | W | | ALL | |
| 0490 | 22 | | GA | | 5-0 | 34-22-36 | D42047P | 20 | | | TB0013X | A016 | BJ | | ALL | |
| 0491 | 22 | | GA | | 4-10 | 34-22-16 | D40523P | 11 | | | TB0013Y | A017 | BJ | | ALL | |
| 0492 | 22 | | GA | | 8-0 | 34-22-36 | D00183 | 17 | | | TB0013Y | A017 | BJ | | 001-099 | |
| 0492 | 22 | | GA | | 10-1 | 34-22-36 | D00771 | 17 | | | TB0013Y | A017 | BJ | | 115-199 | |
| 0501 | 24 | | GK | | 4-8 | 34-22-83 | D00771 | 21 | | | D00775 | 7 | | | 115-199 | |
| 0502 | 24 | | GK | | 4-8 | 34-22-83 | D00771 | 14 | | | D00775 | 4 | | | 115-199 | |
| 0503 | 24 | | GK | | 4-8 | 34-22-83 | D00771 | 12 | | | D00773 | 7 | | | 115-199 | |
| 0504 | 24 | | GK | | 4-8 | 34-22-83 | D00771 | 10 | | | D00773 | 4 | | | 115-199 | |
| 0505 | 20 | | GA | | 9-4 | 34-22-83 | GD01015 | ST.. | 2 | | D00773 | 10 | | | 115-199 | |
| 0506 | 24 | | GK | | 10-6 | 34-22-83 | D00773 | 8 | | | TB0014Y | C010 | BJ | | 115-199 | |
| 0509 | 24 | | GK | | 12-7 | 34-22-83 | D00775 | 8 | | | TB0016Y | A023 | BJ | | 115-199 | |
| 0510 | 20 | | GA | | 9-4 | 34-22-83 | D00775 | 10 | | | GD01015 | ST.. | 2 | | 115-199 | |
| 0511 | 24 | | GK | | 4-9 | 34-22-83 | D41846P | 5 | | | TB0014Y | C010 | BJ | | 115-199 | |
| 0512 | 20 | | GA | | 10-6 | 29-21-32 | D40427P | 18 | | | TB0015X | C022 | BJ | | ALL | |
| 0513 | 22 | | GA | | 6-11 | 29-21-32 | D40209P | 27 | | | D41846P | 1 | | | ALL | |
| 0514 | 22 | | GA | | 6-11 | 29-21-32 | D40209P | 28 | | | D41846P | 2 | | | ALL | |
| 0515 | 22 | | GA | | 7-0 | 29-21-32 | D40427P | 23 | | | D40077P | 14 | | | ALL | |
| 0550 | 24 | | GK | | 8-0 | 34-55-11 | D00795 | 9 | | | TB0013Z | 27 | BJ | | 115-199 | |
| 0551 | 22 | | GA | | 3-2 | 34-55-11 | D00795 | 1 | | | SM00030 | | W | | 115-199 | |
| 0552 | 20 | | GA | | 7-4 | 34-55-11 | D00795 | 2 | | | GD01019 | AC.. | 2 | | 115-199 | |
| 0553 | 20 | | GA | | 7-4 | 34-55-11 | D00795 | 10 | | | GD01019 | ST.. | 2 | | 115-199 | |
| 0554 | 22 | | GA | | 3-11 | 34-55-11 | D41846P | 20 | | | SM00030 | | W | | 115-199 | |
| 0555 | 22 | | GA | | 3-8 | 34-55-11 | D40039P | 50 | | | SM00030 | | W | | 115-199 | |
| 0556 | 24 | | GK | | 5-3 | 34-55-11 | D00795 | 11 | | | D40039P | 54 | | | 115-199 | |
| 0557 | 24 | | GK | | 12-10 | 34-55-21 | D00797 | 9 | | | TB0016Z | 11 | BJ | | 115-199 | |
| 0558 | 24 | | GK | | 6-1 | 34-55-21 | D00797 | 11 | | | D40077P | 55 | | | 115-199 | |
| 0559 | 20 | | GA | | 5-5 | 33-13-11 | D00775 | 1 | | | SM00003 | | W | | 115-199 | |
| 0561 | 20 | | GA | | 3-2 | 33-13-11 | D00797 | 1 | | | SM00015 | | W | | 115-199 | |
| 0562 | 20 | | GA | | 7-2 | 33-13-11 | D00797 | 2 | | | GD01011 | AC.. | 2 | | 115-199 | |
| 0563 | 20 | | GA | | 7-4 | 34-55-11 | D00797 | 3 | | | GD01019 | DC.. | 2 | | 115-199 | |
| 0564 | 24 | | GK | | 4-10 | 34-22-37 | D40281P | 24 | | | D40039P | 33 | | | ALL | |
| 0600 | 24 | | GK | | 4-4 | 31-31-61 | D40039P | 17 | | | TB0013Y | A009 | BJ | | 001-099 | |
| 0601 | 24 | | GK | | 4-4 | 31-31-61 | D40039P | 18 | | | TB0013Y | A010 | BJ | | 001-099 | |
| 0660 | 20 | | GA | | 5-5 | 33-13-11 | D00775 | 2 | | | SM00011 | | W | | 115-199 | |
| 0661 | 24 | | GK | | 7-0 | 34-12-22 | D40427P | 5 | | | D40077P | 40 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|---|---------|----------|---------|-------|------|------|--------|---------|------|-------------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0663 | 24 | | GK | | 7-0 | SPARE | D40427P | 15 | | | | D40077P | 42 | | 115-199 |
| 0665 | 24 | | GK | | 6-8 | SPARE | D40209P | 31 | | | | D40039P | 6 | | 115-199 |
| 0666 | 24 | | GK | | 6-8 | SPARE | D40209P | 32 | | | | D40039P | 7 | | 115-199 |
| 0667 | 22 | | GA | | 7-2 | 32-42-12 | D40427P | 14 | | | | D40523P | 43 | | ALL |
| 0668 | 22 | | GA | | 4-2 | 32-42-12 | SM00017 | | W | | | D40523P | 33 | | ALL |
| 0669 | 22 | | GA | | 6-7 | 32-42-12 | SM00017 | | W | | | TB0014A | C24 | 2 | 001-099 |
| 0669 | 22 | | GA | | 6-7 | 32-42-12 | TB0014A | C24 | 2 | | | SM00017 | | W | 115-199 |
| 0670 | 22 | | GA | | 6-2 | 32-42-12 | TB0014A | A24 | 2 | | | GD01014 | DC.. | 2 | ALL |
| 0680 | 22 | | PA | | 6-10 | 34-61-16 | D40671P | 1 | | | | GD01019 | DC.. | 2 | 115-199 |
| 0681 | 22 | | PA | | 7-0 | 34-61-16 | D40671P | 2 | | | | TB0013Y | A010 | BJ | 115-199 |
| 0682 | 22 | | PA | | 6-10 | 34-61-16 | D40671P | 3 | | | | GD01019 | DC.. | 2 | 115-199 |
| 0683 | 22 | | PA | | 7-0 | 34-61-16 | D40671P | 8 | | | | TB0013Y | A018 | BJ | 115-199 |
| 0684 | 20 | | PA | | 6-0 | 34-61-15 | D40671P | 18 | | | | GD01019 | DC.. | 2 | 115-199 |
| 0703 | 22 | | PA | | 3-9 | 34-61-16 | D40039P | 8 | | | | TB0013Y | A010 | BJ | 115-199 |
| 1001 | 20 | | GT | CM | 13-10 | 33-13-12 | D41878P | 10 | | | | SM00008 | | W | ALL |
| 1001Z | | | | CM | 0-0 | 33-13-12 | D41878P | 24 | | | | GD01013 | AC.. | 2 | ALL |
| 1002 | 20 | | GT | DJ | 10-6 | 29-21-32 | D40427P | 17 | | | | TB0015X | C021 | BJ | ALL |
| 1002Z | | | | DJ | 0-0 | 29-21-32 | D40427P | DED | | | | TB0015X | DED | | ALL |
| 2001B | 22 | | GB | AP | 7-7 | 34-12-11 | D00279 | 23 | | | | D40039P | 23 | | ALL |
| 2001R | 22 | | GB | AP | 0-0 | 34-12-11 | D00279 | 22 | | | | D40039P | 22 | | ALL |
| 2002B | 22 | | GB | AN | 8-2 | 34-12-11 | D00281 | 14 | | | | D40039P | 14 | | 115-199 |
| 2002R | 22 | | GB | AN | 0-0 | 34-12-11 | D00281 | 13 | | | | D40039P | 13 | | 115-199 |
| 2003B | 22 | | GB | AT | 7-11 | 34-12-21 | D00279 | 28 | | | | D40077P | 28 | | ALL |
| 2003R | 22 | | GB | AT | 0-0 | 34-12-21 | D00279 | 27 | | | | D40077P | 27 | | ALL |
| 2004B | 22 | | GB | AR | 8-6 | 34-12-21 | D00281 | 22 | | | | D40077P | 22 | | 115-199 |
| 2004R | 22 | | GB | AR | 0-0 | 34-12-21 | D00281 | 21 | | | | D40077P | 21 | | 115-199 |
| 2008B | 24 | | GL | CF | 6-2 | 33-11-11 | D00898 | 12 | | | | D40850P | 44 | | ALL |
| 2008R | 24 | | GL | CF | 0-0 | 33-11-11 | D00898 | 13 | | | | D40850P | 43 | | ALL |
| 2009B | 24 | | GL | CG | 6-2 | 33-11-11 | D00898 | 4 | | | | D40850P | 4 | | ALL |
| 2009R | 24 | | GL | CG | 0-0 | 33-11-11 | D00898 | 5 | | | | D40850P | 5 | | ALL |
| 2010B | 24 | | GL | CH | 6-2 | 33-11-11 | D00898 | 6 | | | | D40850P | 6 | | ALL |
| 2010R | 24 | | GL | CH | 0-0 | 33-11-11 | D00898 | 7 | | | | D40850P | 7 | | ALL |
| 2011B | 24 | | GL | CI | 4-11 | 33-11-11 | D00898 | 19 | | | | D00890 | 1 | | ALL |
| 2011R | 24 | | GL | CI | 0-0 | 33-11-11 | D00898 | 20 | | | | D00890 | 2 | | ALL |
| 2012B | 24 | | GL | CJ | 4-11 | 33-11-11 | D00898 | 14 | | | | D00890 | 3 | | ALL |
| 2012R | 24 | | GL | CJ | 0-0 | 33-11-11 | D00898 | 15 | | | | D00890 | 4 | | ALL |
| 2013B | 24 | | GL | BR | 8-4 | 34-24-11 | D00275 | 22 | | | | D42047P | 12 | | ALL |
| 2013R | 24 | | GL | BR | 0-0 | 34-24-11 | D00275 | 21 | | | | D42047P | 11 | | ALL |
| 2014B | 24 | | GL | BV | 8-4 | 34-24-11 | D00275 | 12 | | | | D42047P | 33 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 2014R | 24 | GL | BV | | 0-0 | 34-24-11 | D00275 | | 11 | | D42047P | 32 | | | ALL |
| 2015B | 24 | GL | BS | | 8-4 | 34-24-11 | D00275 | | 8 | | D42047P | 8 | | | ALL |
| 2015R | 24 | GL | BS | | 0-0 | 34-24-11 | D00275 | | 7 | | D42047P | 7 | | | ALL |
| 2016B | 24 | GL | BT | | 8-4 | 34-24-11 | D00275 | | 10 | | D42047P | 10 | | | ALL |
| 2016R | 24 | GL | BT | | 0-0 | 34-24-11 | D00275 | | 9 | | D42047P | 9 | | | ALL |
| 2017B | 24 | GL | BU | | 8-4 | 34-24-11 | D00275 | | 14 | | D42047P | 14 | | | ALL |
| 2017R | 24 | GL | BU | | 0-0 | 34-24-11 | D00275 | | 13 | | D42047P | 13 | | | ALL |
| 2018B | 24 | GL | DK | | 9-6 | 33-13-11 | D05254 | | A1 | | D02192 | 5 | | | 115-199 |
| 2018R | 24 | GL | DK | | 0-0 | 33-13-11 | D05254 | | B1 | | D02192 | 6 | | | 115-199 |
| 2019B | 24 | GL | DL | | 6-2 | 33-13-11 | D05254 | | A2 | | SM00005 | | W | | 115-199 |
| 2019R | 24 | GL | DL | | 0-0 | 33-13-11 | D05254 | | B2 | | SM00004 | | W | | 115-199 |
| 2020B | 24 | PL | AX | | 11-3 | 23-51-11 | D40850P | | 30 | | D41834P | 30 | | | 115-199 |
| 2020R | 24 | PL | AX | | 0-0 | 23-51-11 | D40850P | | 31 | | D41834P | 31 | | | 115-199 |
| 2502B | 24 | G2 | AK | | 10-2 | 77-12-11 | D02210 | | 16 | | TB0013X | D006 | BJ | | 001-099 |
| 2502B | 24 | G2 | AK | | 10-2 | 77-12-11 | D02210 | | 16 | | TB0013X | B005 | BJ | | 115-199 |
| 2502R | 24 | G2 | AK | | 0-0 | 77-12-11 | D02210 | | 15 | | TB0013X | C006 | BJ | | 001-099 |
| 2502R | 24 | G2 | AK | | 0-0 | 77-12-11 | D02210 | | 15 | | TB0013X | C005 | BJ | | 115-199 |
| 2502Z | | | AK | | 0-0 | 77-12-11 | D02210 | | DED | | GD01019 | ST.. | 2 | | 001-099 |
| 2502Z | | | AK | | 0-0 | 77-12-11 | D02210 | | DED | | GD01017 | ST.. | 2 | | 115-199 |
| 2504B | 24 | G2 | AI | | 8-3 | 77-12-31 | D02210 | | 24 | | D40077P | 7 | | | 001-099 |
| 2504B | 24 | G2 | AI | | 8-3 | 77-12-31 | D02210 | | 24 | | D40077P | 30 | | | 115-199 |
| 2504R | 24 | G2 | AI | | 0-0 | 77-12-31 | D02210 | | 23 | | D40077P | 8 | | | 001-099 |
| 2504R | 24 | G2 | AI | | 0-0 | 77-12-31 | D02210 | | 23 | | D40077P | 29 | | | 115-199 |
| 2504Z | | | AI | | 0-0 | 77-12-31 | D02210 | | DED | | D40077P | | | AD | 001-099 |
| 2504Z | | | AI | | 0-0 | 77-12-31 | D02210 | | DED | | D40077P | | | AG | 115-199 |
| 2507B | 24 | G2 | BY | | 11-6 | 34-22-15 | D40850P | | 34 | | TB0014Y | C021 | BJ | | ALL |
| 2507R | 24 | G2 | BY | | 0-0 | 34-22-15 | D40850P | | 33 | | TB0014Y | A021 | BJ | | ALL |
| 2507Z | | | BY | | 0-0 | 34-22-15 | D40850P | | DED | | TB0014Y | A020 | BJ | | ALL |
| 2508B | 24 | G2 | AJ | | 10-2 | 77-12-11 | D02208 | | 16 | | TB0013X | B006 | BJ | | 001-099 |
| 2508B | 24 | G2 | AJ | | 10-2 | 77-12-11 | D02208 | | 16 | | TB0013X | C001 | BJ | | 115-199 |
| 2508R | 24 | G2 | AJ | | 0-0 | 77-12-11 | D02208 | | 15 | | TB0013X | A006 | BJ | | 001-099 |
| 2508R | 24 | G2 | AJ | | 0-0 | 77-12-11 | D02208 | | 15 | | TB0013X | D001 | BJ | | 115-199 |
| 2508Z | | | AJ | | 0-0 | 77-12-11 | D02208 | | DED | | GD01019 | ST.. | 2 | | 001-099 |
| 2508Z | | | AJ | | 0-0 | 77-12-11 | D02208 | | DED | | GD01017 | ST.. | 2 | | 115-199 |
| 2509B | 24 | G2 | AH | | 8-5 | 77-12-31 | D02208 | | 24 | | D40523P | 1 | | | 001-099 |
| 2509B | 24 | G2 | AH | | 8-5 | 77-12-31 | D02208 | | 24 | | D40523P | 4 | | | 115-199 |
| 2509R | 24 | G2 | AH | | 0-0 | 77-12-31 | D02208 | | 23 | | D40523P | 2 | | | 001-099 |
| 2509R | 24 | G2 | AH | | 0-0 | 77-12-31 | D02208 | | 23 | | D40523P | 5 | | | 115-199 |
| 2509Z | | | AH | | 0-0 | 77-12-31 | D02208 | | DED | | D40523P | | | AC | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|------------|-------------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0001 | 286N0001 | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 2509Z | | AH | 0-0 | 77-12-31 | D02208 | DED | | | D40523P | | | AF | 115-199 | | |
| 2515B | 24 | G2 CD | 6-2 | 33-11-11 | D00898 | 9 | | | D40850P | 9 | | | ALL | | |
| 2515R | 24 | G2 CD | 0-0 | 33-11-11 | D00898 | 3 | | | D40850P | 3 | | | ALL | | |
| 2515Z | | CD | 0-0 | 33-11-11 | D00898 | | | AK | D40850P | 8 | | | ALL | | |
| 2516B | 24 | G2 CE | 10-3 | 33-11-11 | D00898 | 10 | | | D41878P | 3 | | | ALL | | |
| 2516R | 24 | G2 CE | 0-0 | 33-11-11 | D00898 | 1 | | | D41878P | 4 | | | ALL | | |
| 2516Z | | CE | 0-0 | 33-11-11 | D00898 | | | AK | D41878P | | | AL | ALL | | |
| 3001B | 24 | GM AQ | 7-7 | 34-12-11 | D00279 | 20 | | | D40039P | 20 | | | ALL | | |
| 3001R | 24 | GM AQ | 0-0 | 34-12-11 | D00279 | 19 | | | D40039P | 19 | | | ALL | | |
| 3001Y | 24 | GM AQ | 0-0 | 34-12-11 | D00279 | 21 | | | D40039P | 21 | | | ALL | | |
| 3002B | 24 | GM AO | 8-2 | 34-12-11 | D00281 | 11 | | | D40039P | 11 | | | 115-199 | | |
| 3002R | 24 | GM AO | 0-0 | 34-12-11 | D00281 | 10 | | | D40039P | 10 | | | 115-199 | | |
| 3002Y | 24 | GM AO | 0-0 | 34-12-11 | D00281 | 12 | | | D40039P | 12 | | | 115-199 | | |
| 3003B | 24 | GM AU | 7-11 | 34-12-21 | D00279 | 25 | | | D40077P | 25 | | | ALL | | |
| 3003R | 24 | GM AU | 0-0 | 34-12-21 | D00279 | 24 | | | D40077P | 24 | | | ALL | | |
| 3003Y | 24 | GM AU | 0-0 | 34-12-21 | D00279 | 26 | | | D40077P | 26 | | | ALL | | |
| 3004B | 24 | GM AS | 8-6 | 34-12-21 | D00281 | 19 | | | D40077P | 19 | | | 115-199 | | |
| 3004R | 24 | GM AS | 0-0 | 34-12-21 | D00281 | 18 | | | D40077P | 18 | | | 115-199 | | |
| 3004Y | 24 | GM AS | 0-0 | 34-12-21 | D00281 | 20 | | | D40077P | 20 | | | 115-199 | | |
| 3005B | 22 | GC BQ | 8-4 | 34-24-11 | D00275 | 4 | | | D42047P | 4 | | | ALL | | |
| 3005R | 22 | GC BQ | 0-0 | 34-24-11 | D00275 | 3 | | | D42047P | 3 | | | ALL | | |
| 3005Y | 22 | GC BQ | 0-0 | 34-24-11 | D00275 | 5 | | | D42047P | 5 | | | ALL | | |
| 3006B | 24 | GM BZ | 4-10 | 33-13-11 | D02192 | 5 | | | SM00005 | | W | | 001-099 | | |
| 3006R | 24 | GM BZ | 0-0 | 33-13-11 | D02192 | 6 | | | SM00004 | | W | | 001-099 | | |
| 3006Y | 24 | GM BZ | 0-0 | 33-13-11 | D02192 | 1 | | | SM00006 | | W | | 001-099 | | |
| 3007B | 24 | GM AD | 6-11 | 33-13-11 | D40850P | 14 | | | SM00005 | | W | | ALL | | |
| 3007R | 24 | GM AD | 0-0 | 33-13-11 | D40850P | 13 | | | SM00004 | | W | | ALL | | |
| 3007Y | 24 | GM AD | 0-0 | 33-13-11 | D40850P | 15 | | | SM00006 | | W | | ALL | | |
| 3008B | 24 | GM AE | 5-3 | 33-13-12 | D02914 | 5 | | | SM00005 | | W | | ALL | | |
| 3008R | 24 | GM AE | 0-0 | 33-13-12 | D02914 | 6 | | | SM00004 | | W | | ALL | | |
| 3008Y | 24 | GM AE | 0-0 | 33-13-12 | D02914 | 1 | | | SM00006 | | W | | ALL | | |
| 3013B | 24 | GM BW | 8-0 | 31-25-11 | D00463 | 14 | | | D40850P | 38 | | | 001-099 | | |
| 3013B | 24 | GM BW | 8-9 | 31-25-11 | D00463 | 14 | | | D40850P | 38 | | | 115-199 | | |
| 3013R | 24 | GM BW | 0-0 | 31-25-11 | D00463 | 13 | | | D40850P | 39 | | | ALL | | |
| 3013Y | 24 | GM BW | 0-0 | 31-25-11 | D00463 | 15 | | | D40850P | 40 | | | ALL | | |
| 3502B | 24 | G3 CK | 10-3 | 33-11-11 | D00898 | 18 | | | D41878P | 5 | | | ALL | | |
| 3502R | 24 | G3 CK | 0-0 | 33-11-11 | D00898 | 11 | | | D41878P | 6 | | | ALL | | |
| 3502Y | 24 | G3 CK | 0-0 | 33-11-11 | D00898 | 8 | | | D41878P | 7 | | | ALL | | |
| 3502Z | | CK | 0-0 | 33-11-11 | D00898 | | | AK | D41878P | | | AL | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 13

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W0000
Page 14
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|---------|----------|---------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | |
| 5021R | 24 | G2 | BE | | 0-0 | 34-13-11 | D40031P | | 25 | TB0014Y | A013 | BJ | | ALL |
| 5021Z | | | BE | | 0-0 | 34-13-11 | D40031P | | 27 | GD01011 | ST.. | 2 | | ALL |
| 5022B | 24 | G2 | BF | | 4-10 | 34-13-11 | D40077P | | 3 | TB0014Y | C014 | BJ | | ALL |
| 5022R | 24 | G2 | BF | | 0-0 | 34-13-11 | D40077P | | 2 | TB0014Y | A014 | BJ | | ALL |
| 5022Z | | | BF | | 0-0 | 34-13-11 | D40077P | | 1 | GD01011 | ST.. | 2 | | ALL |
| 5028B | 24 | G2 | BP | | 8-3 | 34-22-82 | D00187 | | 29 | D42047P | | 29 | | ALL |
| 5028R | 24 | G2 | BP | | 0-0 | 34-22-82 | D00187 | | 28 | D42047P | | 28 | | ALL |
| 5028Z | | | BP | | 0-0 | 34-22-82 | D00187 | | DED | D42047P | | | AH | ALL |
| 5029B | 24 | G2 | BO | | 8-0 | 34-22-82 | D00187 | | 31 | D40031P | | 36 | | ALL |
| 5029R | 24 | G2 | BO | | 0-0 | 34-22-82 | D00187 | | 30 | D40031P | | 35 | | ALL |
| 5029Z | | | BO | | 0-0 | 34-22-82 | D00187 | | DED | D40031P | | | AJ | ALL |
| 5030B | 24 | G2 | BX | | 8-5 | 31-25-11 | D00463 | | 23 | D40031P | | 45 | | 001-099 |
| 5030B | 24 | G2 | BX | | 6-6 | 31-25-11 | D00463 | | 23 | D40031P | | 45 | | 115-199 |
| 5030R | 24 | G2 | BX | | 0-0 | 31-25-11 | D00463 | | 24 | D40031P | | 44 | | ALL |
| 5030Z | | | BX | | 0-0 | 31-25-11 | D00463 | | DED | D40031P | | | AB | ALL |
| 5032B | 24 | G2 | BG | | 6-1 | 34-22-81 | D00183 | | 42 | D40077P | | 16 | | 001-099 |
| 5032B | 24 | G2 | BG | | 8-3 | 34-22-83 | D00771 | | 42 | D40077P | | 16 | | 115-199 |
| 5032R | 24 | G2 | BG | | 0-0 | 34-22-81 | D00183 | | 41 | D40077P | | 15 | | 001-099 |
| 5032R | 24 | G2 | BG | | 0-0 | 34-22-83 | D00771 | | 41 | D40077P | | 15 | | 115-199 |
| 5032Z | | | BG | | 0-0 | 34-22-81 | D00183 | | DED | D40077P | | | AA | 001-099 |
| 5032Z | | | BG | | 0-0 | 34-22-83 | D00771 | | DED | D40077P | | | AA | 115-199 |
| 5033B | 24 | G2 | BH | | 12-10 | 34-22-81 | D00183 | | 14 | TB0016Y | C014 | BJ | | 001-099 |
| 5033R | 24 | G2 | BH | | 0-0 | 34-22-81 | D00183 | | 13 | TB0016Y | A014 | BJ | | 001-099 |
| 5033Z | | | BH | | 0-0 | 34-22-81 | D00183 | | DED | GD01242 | ST.. | 2 | | 001-099 |
| 5034B | 24 | G2 | BI | | 12-10 | 34-22-81 | D00183 | | 49 | TB0016Y | C013 | BJ | | 001-099 |
| 5034B | 24 | G2 | BI | | 12-5 | 34-22-83 | D00771 | | 49 | TB0016Y | C013 | BJ | | 115-199 |
| 5034R | 24 | G2 | BI | | 0-0 | 34-22-81 | D00183 | | 48 | TB0016Y | A013 | BJ | | 001-099 |
| 5034R | 24 | G2 | BI | | 0-0 | 34-22-83 | D00771 | | 48 | TB0016Y | A013 | BJ | | 115-199 |
| 5034Z | | | BI | | 0-0 | 34-22-81 | D00183 | | DED | GD01242 | ST.. | 2 | | 001-099 |
| 5034Z | | | BI | | 0-0 | 34-22-83 | D00771 | | DED | GD01242 | ST.. | 2 | | 115-199 |
| 5035B | 24 | G2 | CA | | 8-2 | 34-22-81 | D00183 | | 10 | TB0014Y | C015 | BJ | | 001-099 |
| 5035R | 24 | G2 | CA | | 0-0 | 34-22-81 | D00183 | | 9 | TB0014Y | A015 | BJ | | 001-099 |
| 5035Z | | | CA | | 0-0 | 34-22-81 | D00183 | | DED | GD01013 | ST.. | 2 | | 001-099 |
| 5036B | 24 | G2 | CB | | 8-2 | 34-22-81 | D00183 | | 39 | TB0014Y | C016 | BJ | | 001-099 |
| 5036B | 24 | G2 | CB | | 10-4 | 34-22-83 | D00771 | | 39 | TB0014Y | C016 | BJ | | 115-199 |
| 5036R | 24 | G2 | CB | | 0-0 | 34-22-81 | D00183 | | 38 | TB0014Y | A016 | BJ | | 001-099 |
| 5036R | 24 | G2 | CB | | 0-0 | 34-22-83 | D00771 | | 38 | TB0014Y | A016 | BJ | | 115-199 |
| 5036Z | | | CB | | 0-0 | 34-22-81 | D00183 | | DED | GD01013 | ST.. | 2 | | 001-099 |
| 5036Z | | | CB | | 0-0 | 34-22-83 | D00771 | | DED | GD01013 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5037B | 24 | G2 | BM | | 5-0 | 34-22-81 | D40031P | 33 | | | TB0014Y | C017 | BJ | | 001-099 |
| 5037B | 24 | G2 | BM | | 5-0 | 34-22-83 | D40031P | 33 | | | TB0014Y | C017 | BJ | | 115-199 |
| 5037R | 24 | G2 | BM | | 0-0 | 34-22-81 | D40031P | 32 | | | TB0014Y | A017 | BJ | | 001-099 |
| 5037R | 24 | G2 | BM | | 0-0 | 34-22-83 | D40031P | 32 | | | TB0014Y | A017 | BJ | | 115-199 |
| 5037Z | | | BM | | 0-0 | 34-22-81 | D40031P | 34 | | | GD01013 | ST.. | 2 | | 001-099 |
| 5037Z | | | BM | | 0-0 | 34-22-83 | GD01013 | ST.. | 2 | | D40031P | 34 | | | 115-199 |
| 5038B | 24 | G2 | CC | | 8-2 | 34-22-81 | D00183 | 19 | | | TB0014Y | C017 | BJ | | 001-099 |
| 5038B | 24 | G2 | CC | | 10-4 | 34-22-83 | D00771 | 19 | | | TB0014Y | C017 | BJ | | 115-199 |
| 5038R | 24 | G2 | CC | | 0-0 | 34-22-81 | D00183 | 18 | | | TB0014Y | A017 | BJ | | 001-099 |
| 5038R | 24 | G2 | CC | | 0-0 | 34-22-83 | D00771 | 18 | | | TB0014Y | A017 | BJ | | 115-199 |
| 5038Z | | | CC | | 0-0 | 34-22-81 | D00183 | DED | | | GD01013 | ST.. | 2 | | 001-099 |
| 5038Z | | | CC | | 0-0 | 34-22-83 | D00771 | DED | | | GD01013 | ST.. | 2 | | 115-199 |
| 5039B | 24 | G2 | BJ | | 8-2 | 34-22-81 | D00183 | 45 | | | TB0014Y | C018 | BJ | | 001-099 |
| 5039B | 24 | G2 | BJ | | 10-4 | 34-22-83 | D00771 | 45 | | | TB0014Y | C018 | BJ | | 115-199 |
| 5039R | 24 | G2 | BJ | | 0-0 | 34-22-81 | D00183 | 44 | | | TB0014Y | A018 | BJ | | 001-099 |
| 5039R | 24 | G2 | BJ | | 0-0 | 34-22-83 | D00771 | 44 | | | TB0014Y | A018 | BJ | | 115-199 |
| 5039Z | | | BJ | | 0-0 | 34-22-81 | D00183 | DED | | | GD01013 | ST.. | 2 | | 001-099 |
| 5039Z | | | BJ | | 0-0 | 34-22-83 | D00771 | DED | | | GD01013 | ST.. | 2 | | 115-199 |
| 5040B | 24 | G2 | BN | | 5-3 | 34-22-81 | D42047P | 15 | | | TB0014Y | C018 | BJ | | 001-099 |
| 5040B | 24 | G2 | BN | | 5-3 | 34-22-83 | D42047P | 15 | | | TB0014Y | C018 | BJ | | 115-199 |
| 5040R | 24 | G2 | BN | | 0-0 | 34-22-81 | D42047P | 16 | | | TB0014Y | A018 | BJ | | 001-099 |
| 5040R | 24 | G2 | BN | | 0-0 | 34-22-83 | D42047P | 16 | | | TB0014Y | A018 | BJ | | 115-199 |
| 5040Z | | | BN | | 0-0 | 34-22-81 | D42047P | 17 | | | GD01013 | ST.. | 2 | | 001-099 |
| 5040Z | | | BN | | 0-0 | 34-22-83 | D42047P | 17 | | | GD01013 | ST.. | 2 | | 115-199 |
| 5041B | 24 | G2 | BK | | 5-0 | 34-22-81 | D40031P | 23 | | | TB0014Y | C015 | BJ | | 001-099 |
| 5041R | 24 | G2 | BK | | 0-0 | 34-22-81 | D40031P | 22 | | | TB0014Y | A015 | BJ | | 001-099 |
| 5041Z | | | BK | | 0-0 | 34-22-81 | D40031P | 24 | | | GD01013 | ST.. | 2 | | 001-099 |
| 5042B | 24 | G2 | BL | | 5-0 | 34-22-81 | D40031P | 42 | | | TB0014Y | C016 | BJ | | 001-099 |
| 5042B | 24 | G2 | BL | | 5-0 | 34-22-83 | D40031P | 42 | | | TB0014Y | C016 | BJ | | 115-199 |
| 5042R | 24 | G2 | BL | | 0-0 | 34-22-81 | D40031P | 41 | | | TB0014Y | A016 | BJ | | 001-099 |
| 5042R | 24 | G2 | BL | | 0-0 | 34-22-83 | D40031P | 41 | | | TB0014Y | A016 | BJ | | 115-199 |
| 5042Z | | | BL | | 0-0 | 34-22-81 | D40031P | 43 | | | GD01013 | ST.. | 2 | | 001-099 |
| 5042Z | | | BL | | 0-0 | 34-22-83 | D40031P | 43 | | | GD01013 | ST.. | 2 | | 115-199 |
| 5044B | 24 | G2 | DD | | 12-5 | 34-22-83 | D00771 | 32 | | | TB0016Y | C024 | BJ | | 115-199 |
| 5044R | 24 | G2 | DD | | 0-0 | 34-22-83 | D00771 | 31 | | | TB0016Y | A024 | BJ | | 115-199 |
| 5044Z | | | DD | | 0-0 | 34-22-83 | D00771 | DED | | | GD01242 | ST.. | 2 | | 115-199 |
| 5046B | 24 | G2 | DB | | 8-0 | 34-55-11 | D00795 | 7 | | | TB0013Y | A013 | BJ | | 115-199 |
| 5046R | 24 | G2 | DB | | 0-0 | 34-55-11 | D00795 | 4 | | | TB0013Y | C013 | BJ | | 115-199 |
| 5046Z | | | DB | | 0-0 | 34-55-11 | D00795 | DED | | | GD01019 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0001 | 286N0001 | | | CAPT'S INST PANELS(P1-1,P1-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5047B | 24 | G2 | DC | | 4-4 | 34-55-11 | D40039P | 52 | | | TB0013Y | A013 | BJ | | 115-199 |
| 5047R | 24 | G2 | DC | | 0-0 | 34-55-11 | D40039P | 51 | | | TB0013Y | C013 | BJ | | 115-199 |
| 5047Z | | | DC | | 0-0 | 34-55-11 | D40039P | 53 | | | GD01019 | ST.. | 2 | | 115-199 |
| 5048B | 24 | G2 | DA | | 12-10 | 34-55-21 | D00797 | 7 | | | TB0015Y | A006 | BJ | | 115-199 |
| 5048R | 24 | G2 | DA | | 0-0 | 34-55-21 | D00797 | 4 | | | TB0015Y | C006 | BJ | | 115-199 |
| 5048Z | | | DA | | 0-0 | 34-55-21 | D00797 | DED | | | GD01248 | ST.. | 2 | | 115-199 |
| 5050B | 24 | G2 | CN | | 12-10 | 34-22-81 | D00183 | 32 | | | TB0016Y | C025 | BJ | | 001-099 |
| 5050R | 24 | G2 | CN | | 0-0 | 34-22-81 | D00183 | 31 | | | TB0016Y | A025 | BJ | | 001-099 |
| 5050Z | | | CN | | 0-0 | 34-22-81 | D00183 | DED | | | GD01248 | ST.. | 2 | | 001-099 |
| 5055B | 24 | G2 | CP | | 5-0 | 34-22-28 | D40031P | 51 | | | TB0014Y | C017 | BJ | | 115-199 |
| 5055R | 24 | G2 | CP | | 0-0 | 34-22-28 | D40031P | 50 | | | TB0014Y | A017 | BJ | | 115-199 |
| 5055Z | | | CP | | 0-0 | 34-22-28 | D40031P | 52 | | | GD01013 | ST.. | 2 | | 115-199 |
| FRAA | | | | | 0-0 | 34-22-81 | D40077P | | | AA | D40077P | 17 | | | 001-099 |
| FRAA | | | | | 0-0 | 34-22-83 | D40077P | | | AA | D40077P | 17 | | | 115-199 |
| FRAB | | | | | 0-0 | 31-25-11 | D40031P | 46 | | | D40031P | | | AB | ALL |
| FRAC | | | | | 0-0 | 77-12-31 | D40523P | 3 | | | D40523P | | | AC | 001-099 |
| FRAD | | | | | 0-0 | 77-12-31 | D40077P | 9 | | | D40077P | | | AD | 001-099 |
| FRAF | | | | | 0-0 | 77-12-31 | D40523P | | | AF | D40523P | 6 | | | 115-199 |
| FRAG | | | | | 0-0 | 77-12-31 | D40077P | | | AG | D40077P | 31 | | | 115-199 |
| FRAH | | | | | 0-0 | 34-22-82 | D42047P | 30 | | | D42047P | | | AH | ALL |
| FRAJ | | | | | 0-0 | 34-22-82 | D40031P | 37 | | | D40031P | | | AJ | ALL |
| FRAL | | | | | 0-0 | 33-11-11 | D41878P | 39 | | | D41878P | | | AL | ALL |
| PB01 | | | | | 0-0 | 33-13-12 | D02884 | G1 | | | D02884 | G3 | | | ALL |
| W0002 | 286N0002 | | | P3-1 INTERNAL-LANDING GEAR SYSTEM A | | | | | | | | | | | |
| 0001 | 22 | GA | | | 1-4 | 27-51-21 | D40836J | 24 | | | TB0071Z | 5 | BJ | | ALL |
| 0002 | 24 | GK | | | 1-6 | 27-51-11 | TB0071Y | A001 | BJ | | S10254 | 8 | 1A | | ALL |
| 0003 | 24 | GK | | | 1-6 | 27-51-11 | TB0071Z | 5 | BJ | | S10254 | 9 | 1A | | ALL |
| 0004 | 24 | GK | | | 1-7 | 27-51-11 | TB0071Z | 5 | BJ | | S10255 | 9 | 1A | | ALL |
| 0005 | 24 | GK | | | 1-6 | 27-51-11 | TB0071Y | A001 | BJ | | S10255 | 8 | 1A | | ALL |
| 0006 | 24 | GK | | | 1-5 | 27-51-11 | TB0071Y | A001 | BJ | | S10256 | AA | 1A | | ALL |
| 0007 | 24 | GK | | | 1-7 | 27-51-11 | D40834J | 1 | | | S10256 | AD | 1A | | ALL |
| 0008 | 24 | GK | | | 1-7 | 27-51-11 | D40834J | 2 | | | S10256 | AE | 1A | | ALL |
| 0009 | 24 | GK | | | 1-7 | 27-51-11 | D40834J | 3 | | | S10256 | AF | 1A | | ALL |
| 0010 | 24 | GK | | | 1-7 | 27-51-11 | D40834J | 4 | | | S10256 | AG | 1A | | ALL |
| 0011 | 24 | GK | | | 1-7 | 27-51-11 | D40834J | 5 | | | S10256 | AH | 1A | | ALL |
| 0012 | 24 | GK | | | 1-7 | 27-51-11 | D40834J | 6 | | | S10256 | AJ | 1A | | ALL |
| 0013 | 24 | GK | | | 1-7 | 27-51-11 | D40834J | 7 | | | S10256 | AB | 1A | | 115-199 |
| 0014 | 24 | GK | | | 1-7 | 27-51-11 | D40834J | 8 | | | S10256 | AC | 1A | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0002 | 286N0002 | | | P3-1 INTERNAL-LANDING GEAR SYSTEM A (continued) | | | | | | | | | | | |
| 0015 | 24 | | GK | | 1-8 | 27-51-11 | D40834J | | 33 | | S10254 | 7 | 1A | | ALL |
| 0016 | 22 | | GA | | 1-8 | 27-51-21 | D40836J | | 1 | | S10254 | 5 | 1A | | ALL |
| 0017 | 22 | | GA | | 1-6 | 27-51-21 | TB0071Z | | 5 | BJ | S10254 | 3 | 1A | | ALL |
| 0018 | 22 | | GA | | 1-8 | 27-51-21 | D40836J | | 2 | | S10254 | 4 | 1A | | ALL |
| 0019 | 22 | | GA | | 1-6 | 27-51-21 | TB0071Y | C001 | BJ | | S10254 | 2 | 1A | | ALL |
| 0020 | 22 | | GA | | 1-6 | 27-51-21 | TB0071Z | | 5 | BJ | S10254 | 6 | 1A | | ALL |
| 0021 | 24 | | GK | | 1-8 | 27-51-11 | D40834J | | 34 | | S10255 | 7 | 1A | | ALL |
| 0022 | 22 | | GA | | 1-8 | 27-51-21 | D40836J | | 3 | | S10255 | 5 | 1A | | ALL |
| 0023 | 22 | | GA | | 1-7 | 27-51-21 | TB0071Z | | 5 | BJ | S10255 | 3 | 1A | | ALL |
| 0024 | 22 | | GA | | 1-8 | 27-51-21 | D40836J | | 4 | | S10255 | 4 | 1A | | ALL |
| 0025 | 22 | | GA | | 1-6 | 27-51-21 | TB0071Y | C001 | BJ | | S10255 | 2 | 1A | | ALL |
| 0026 | 22 | | GA | | 1-7 | 27-51-21 | TB0071Z | | 5 | BJ | S10255 | 6 | 1A | | ALL |
| 0027 | 22 | | GA | | 1-4 | 27-51-21 | D40836J | | 29 | | TB0071Y | C001 | BJ | | ALL |
| 0031 | 22 | | GA | | 1-8 | 27-51-21 | D40836J | | 10 | | S10255 | 1 | 1A | | ALL |
| 0032 | 22 | | GA | | 2-6 | 34-22-36 | D40834J | | 37 | | S00616 | 1NO | Z2 | | ALL |
| 0033 | 20 | | GA | | 2-2 | 34-22-36 | S00616 | | 1C | Z2 | GD01078 | ST.. | E | *1 | ALL |
| 0034 | 20 | | GA | | 2-2 | 34-22-36 | S00616 | | 4C | Z2 | GD01078 | ST.. | E | *1 | ALL |
| 0035 | 22 | | GA | | 2-6 | 34-22-36 | D40834J | | 39 | | S00616 | 3NC | Z2 | | ALL |
| 0036 | 20 | | GA | | 2-2 | 34-22-36 | S00616 | | 3C | Z2 | GD01078 | ST.. | E | *1 | ALL |
| 0037 | 22 | | GA | | 2-6 | 34-22-36 | S00616 | | 4NC | Z2 | D40834J | 38 | | | ALL |
| 0038 | 20 | | GA | | 2-6 | 33-13-21 | L00574 | =P | B | | TB0070Z | 4 | BJ | | ALL |
| 0039 | 20 | | GA | | 2-6 | 33-13-21 | L00574 | =G | G | | TB0070Z | 3 | BJ | | ALL |
| 0040 | 20 | | GA | | 1-5 | 33-13-21 | S10231 | | 13 | 1A | TB0070Z | 4 | BJ | | ALL |
| 0041 | 20 | | GA | | 1-4 | 33-13-21 | S10231 | | 15 | 1A | TB0070Z | 3 | BJ | | ALL |
| 0042 | 20 | | GA | | 1-8 | 33-13-21 | D40834J | | 29 | | L00370 | =P | B | | ALL |
| 0043 | 20 | | GA | | 1-7 | 33-13-21 | L00370 | =G | G | | TB0070Z | 3 | BJ | | ALL |
| 0044 | 20 | | GA | | 1-8 | 33-13-21 | S10254 | | 13 | 1A | TB0070Z | 4 | BJ | | ALL |
| 0045 | 20 | | GA | | 1-7 | 33-13-21 | S10254 | | 15 | 1A | TB0070Z | 3 | BJ | | ALL |
| 0046 | 20 | | GA | | 1-8 | 33-13-21 | S10255 | | 13 | 1A | TB0070Z | 4 | BJ | | ALL |
| 0047 | 20 | | GA | | 1-8 | 33-13-21 | S10255 | | 15 | 1A | TB0070Z | 3 | BJ | | ALL |
| 0048 | 20 | | GA | | 1-6 | 33-13-21 | S10172 | | 13 | 1A | TB0070Z | 4 | BJ | | ALL |
| 0049 | 20 | | GA | | 1-5 | 33-13-21 | S10172 | | 15 | 1A | TB0070Z | 3 | BJ | | ALL |
| 0050 | 22 | | GA | | 1-6 | 33-16-51 | S10260 | | 13 | 1A | D42174J | 5 | | | 115-199 |
| 0051 | 22 | | GA | | 1-6 | 33-16-51 | S10260 | | 14 | 1A | D42174J | 6 | | | 115-199 |
| 0052 | 20 | | GA | | 1-7 | 33-13-21 | D40834J | | 27 | | TB0070Z | 4 | BJ | | ALL |
| 0053 | 20 | | GA | | 1-6 | 33-13-21 | D40834J | | 28 | | TB0070Z | 3 | BJ | | ALL |
| 0054 | 22 | | GA | | 2-2 | 33-16-51 | D40836J | | 8 | | L00445 | 3 | 1A | | ALL |
| 0055 | 22 | | GA | | 1-7 | 33-16-51 | D40836J | | 13 | | TB0070Z | 5 | BJ | | ALL |
| 0056 | 22 | | GA | | 2-2 | 33-16-51 | L00400 | | 3 | 1A | TB0070Z | 5 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0002 | 286N0002 | | | P3-1 INTERNAL-LANDING GEAR SYSTEM A (continued) | | | | | | | | | | | |
| 0057 | 22 | GA | | | 2-2 | 33-16-61 | L00398 | 1 | 1A | | TB0071Z | 6 | BJ | | ALL |
| 0058 | 22 | GA | | | 2-1 | 33-16-61 | L00399 | 1 | 1A | | TB0071Z | 6 | BJ | | ALL |
| 0059 | 22 | GA | | | 2-0 | 33-16-61 | L00400 | 1 | 1A | | TB0071Z | 6 | BJ | | ALL |
| 0060 | 22 | GA | | | 2-3 | 33-16-51 | L00397 | 3 | 1A | | TB0070Z | 5 | BJ | | ALL |
| 0061 | 22 | GA | | | 2-3 | 33-16-51 | L00398 | 3 | 1A | | TB0070Z | 5 | BJ | | ALL |
| 0062 | 22 | GA | | | 1-6 | 33-16-51 | D40836J | 55 | | | SM00005 | | 9 | | ALL |
| 0063 | 22 | GA | | | 2-2 | 33-16-51 | L00396 | 3 | 1A | | TB0070Z | 5 | BJ | | ALL |
| 0064 | 22 | GA | | | 2-3 | 33-16-51 | L00399 | 3 | 1A | | TB0070Z | 5 | BJ | | ALL |
| 0065 | 22 | GA | | | 1-6 | 33-16-51 | TB0070Z | 5 | BJ | | SM00006 | | 9 | | ALL |
| 0066 | 22 | GA | | | 2-2 | 33-16-51 | D40836J | 9 | | | L00445 | 1 | 1A | | ALL |
| 0067 | 22 | GA | | | 1-4 | 33-16-31 | D40834J | 10 | | | TB0071Y | C002 | BJ | | ALL |
| 0068 | 22 | GA | | | 1-2 | 33-16-51 | L00434 | 1 | 1A | | SM00005 | | 9 | | ALL |
| 0069 | 22 | GA | | | 1-2 | 33-16-51 | L00433 | 1 | 1A | | SM00005 | | 9 | | ALL |
| 0070 | 22 | GA | | | 2-1 | 33-16-61 | L00397 | 1 | 1A | | TB0071Z | 6 | BJ | | ALL |
| 0071 | 22 | GA | | | 2-0 | 33-16-61 | L00396 | 1 | 1A | | TB0071Z | 6 | BJ | | ALL |
| 0072 | 22 | GA | | | 1-4 | 33-16-61 | D40834J | 11 | | | TB0071Z | 6 | BJ | | ALL |
| 0073 | 22 | GA | | | 1-5 | 33-16-41 | D40834J | 12 | | | TB0071Y | A003 | BJ | | ALL |
| 0074 | 22 | GA | | | 1-2 | 33-16-51 | L00433 | 3 | 1A | | SM00006 | | 9 | | ALL |
| 0075 | 22 | GA | | | 1-2 | 33-16-51 | L00434 | 3 | 1A | | SM00006 | | 9 | | ALL |
| 0076 | 24 | GK | | | 2-2 | 27-51-41 | D40836J | 17 | | | L00433 | 2 | 1A | | ALL |
| 0077 | 24 | GK | | | 2-2 | 27-51-41 | D40836J | 18 | | | L00434 | 2 | 1A | | ALL |
| 0078 | 24 | GK | | | 1-7 | 27-51-61 | TB0071Y | A004 | BJ | | S10254 | 11 | 1A | | ALL |
| 0079 | 24 | GK | | | 1-7 | 27-51-61 | TB0071Y | C004 | BJ | | S10254 | 12 | 1A | | ALL |
| 0080 | 24 | GK | | | 1-7 | 27-51-61 | TB0071Y | A004 | BJ | | S10255 | 11 | 1A | | ALL |
| 0081 | 24 | GK | | | 1-7 | 27-51-61 | TB0071Y | C004 | BJ | | S10255 | 12 | 1A | | ALL |
| 0082 | 24 | GK | | | 1-5 | 27-51-61 | TB0071Y | A004 | BJ | | S10256 | BA | 1A | | ALL |
| 0083 | 24 | GK | | | 1-7 | 27-51-61 | D40834J | 13 | | | S10256 | BD | 1A | | ALL |
| 0084 | 24 | GK | | | 1-7 | 27-51-61 | D40834J | 14 | | | S10256 | BE | 1A | | ALL |
| 0085 | 24 | GK | | | 1-7 | 27-51-61 | D40834J | 15 | | | S10256 | BF | 1A | | ALL |
| 0086 | 24 | GK | | | 1-7 | 27-51-61 | D40834J | 16 | | | S10256 | BG | 1A | | ALL |
| 0087 | 24 | GK | | | 1-7 | 27-51-61 | D40834J | 17 | | | S10256 | BH | 1A | | ALL |
| 0088 | 24 | GK | | | 1-7 | 27-51-61 | D40834J | 18 | | | S10256 | BJ | 1A | | ALL |
| 0089 | 24 | GK | | | 1-7 | 27-51-61 | D40834J | 19 | | | S10256 | BB | 1A | | ALL |
| 0090 | 24 | GK | | | 1-7 | 27-51-61 | D40834J | 20 | | | S10256 | BC | 1A | | ALL |
| 0091 | 24 | GK | | | 1-5 | 27-51-61 | D40834J | 21 | | | TB0071Y | C004 | BJ | | ALL |
| 0092 | 24 | GK | | | 1-8 | 27-51-61 | D40834J | 35 | | | S10254 | 10 | 1A | | ALL |
| 0093 | 24 | GK | | | 1-8 | 27-51-61 | D40834J | 36 | | | S10255 | 10 | 1A | | ALL |
| 0096 | 20 | GA | | | 1-6 | 32-35-11 | D42174J | 1 | | | S10260 | 1 | C | | 001-099 |
| 0096 | 20 | GA | | | 1-6 | 32-35-11 | D42174J | 1 | | | S10260 | 2 | 1A | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0002 | 286N0002 | | | | P3-1 INTERNAL-LANDING GEAR SYSTEM A (continued) | | | | | | | | | | | |
| 0097 | 20 | | GA | | 1-6 | 32-35-11 | | D42174J | | 2 | | S10260 | 3 | C | | 001-099 |
| 0097 | 20 | | GA | | 1-6 | 32-35-11 | | D42174J | | 2 | | S10260 | 1 | 1A | | 115-199 |
| 0098 | 20 | | GA | | 1-6 | 32-35-11 | | D42174J | | 3 | | S10260 | 2 | C | | 001-099 |
| 0098 | 20 | | GA | | 1-6 | 32-35-11 | | D42174J | | 3 | | S10260 | 3 | 1A | | 115-199 |
| 0099 | 20 | | GA | | 1-6 | 32-35-11 | | D42174J | | 4 | | S10260 | 15 | 1A | | 115-199 |
| 0103 | 22 | | GA | | 1-2 | 32-61-12 | | SM00001 | | | W | L00396 | 2 | 1A | | ALL |
| 0104 | 22 | | GA | | 1-3 | 32-61-12 | | SM00002 | | | W | L00397 | 2 | 1A | | ALL |
| 0109 | 22 | | GA | | 2-3 | 32-61-21 | | D40834J | | 30 | | L00398 | 2 | 1A | | ALL |
| 0110 | 22 | | GA | | 2-3 | 32-61-21 | | D40834J | | 31 | | L00399 | 2 | 1A | | ALL |
| 0111 | 22 | | GA | | 2-2 | 32-61-21 | | D40834J | | 32 | | L00400 | 2 | 1A | | ALL |
| 0112 | 24 | | GK | | 1-6 | 34-46-11 | | D40836J | | 30 | | S10172 | 11 | 1A | | ALL |
| 0114 | 24 | | GK | | 1-5 | 34-46-11 | | D40836J | | 32 | | S10231 | 5 | 1A | | ALL |
| 0115 | 24 | | GK | | 1-6 | SPARE | | D40836J | | 33 | | S10172 | 7 | 1A | | 115-199 |
| 0116 | 24 | | GK | | 1-6 | 34-46-11 | | S10172 | | 12 | 1A | D40836J | 26 | | | ALL |
| 0117 | 24 | | GK | | 1-5 | 34-46-11 | | S10231 | | 6 | 1A | D40836J | 27 | | | ALL |
| 0118 | 22 | | GA | | 1-4 | 32-31-11 | | D40834J | | 23 | | TB0071A | C007 | 2 | | ALL |
| 0119 | 22 | | GA | | 1-4 | 32-31-11 | | D40834J | | 24 | | TB0071A | C007 | 2 | | ALL |
| 0120 | 22 | | GA | | 2-2 | 26-17-11 | | D40836J | | 7 | | L00445 | 2 | 1A | | ALL |
| 0121 | 20 | | GA | | 1-7 | 32-35-11 | | D42174J | | 15 | | GD01078 | ST.. | E | | ALL |
| 0122 | 24 | | GK | | 1-5 | 31-51-31 | | D40836J | | 6 | | S10231 | 2 | 1A | | ALL |
| 0123 | 24 | | GK | | 1-5 | 31-51-31 | | S10231 | | 3 | 1A | TB0070Z | 6 | BJ | | ALL |
| 0124 | 20 | | GA | | 1-0 | 31-51-31 | | TB0070Z | | 3 | BJ | TB0070Z | 6 | BJ | | ALL |
| 0125 | 24 | | GK | | 1-4 | 27-51-11 | | D40834J | | 22 | | TB0071Y | A001 | BJ | | ALL |
| 0126 | 22 | | GA | | 2-2 | 33-16-51 | | L00530 | | 3 | 1A | D40836J | 12 | | | 115-199 |
| 0127 | 22 | | GA | | 1-4 | 32-31-11 | | D40834J | | 25 | | TB0071A | A007 | 2 | | ALL |
| 0128 | 22 | | GA | | 2-2 | 33-16-51 | | D40836J | | 11 | | L00530 | 1 | 1A | | 115-199 |
| 0129 | 22 | | GA | | 1-4 | 32-31-11 | | D40834J | | 26 | | TB0071A | A007 | 2 | | ALL |
| 0130 | 22 | | GA | | 2-2 | 32-46-11 | | L00530 | | 2 | 1A | D40836J | 15 | | | 115-199 |
| 0131 | 22 | | GA | | 1-2 | 32-61-12 | | L00396 | | 5 | 1A | SM00001 | | W | | ALL |
| 0132 | 22 | | GA | | 1-3 | 32-61-12 | | L00397 | | 5 | 1A | SM00002 | | W | | ALL |
| 0133 | 22 | | GA | | 1-6 | 32-61-12 | | D40836J | | 21 | | SM00001 | | W | | ALL |
| 0134 | 22 | | GA | | 1-6 | 32-61-12 | | D40836J | | 22 | | SM00002 | | W | | ALL |
| 0135 | 22 | | GA | | 2-3 | 32-61-21 | | L00398 | | 5 | 1A | D40836J | 50 | | | ALL |
| 0136 | 22 | | GA | | 2-3 | 32-61-21 | | L00399 | | 5 | 1A | D40836J | 51 | | | ALL |
| 0137 | 22 | | GA | | 2-2 | 32-61-21 | | L00400 | | 5 | 1A | D40836J | 52 | | | ALL |
| 0138 | 22 | | GA | | 1-4 | 33-16-31 | | TB0071Y | C002 | BJ | | SM00003 | | W | | ALL |
| 0139 | 22 | | GA | | 1-2 | 33-16-31 | | L00396 | | 4 | 1A | SM00003 | | W | | ALL |
| 0140 | 22 | | GA | | 1-3 | 33-16-31 | | L00397 | | 4 | 1A | SM00003 | | W | | ALL |
| 0141 | 22 | | GA | | 1-3 | 33-16-31 | | L00399 | | 4 | 1A | SM00003 | | W | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0002 | 286N0002 | | | P3-1 INTERNAL-LANDING GEAR SYSTEM A (continued) | | | | | | | | | | | |
| 0142 | 22 | | GA | | 1-2 | 33-16-31 | L00400 | 4 | 1A | | SM00003 | | W | | ALL |
| 0143 | 22 | | GA | | 1-4 | 33-16-31 | L00398 | 4 | 1A | | SM00003 | | W | | ALL |
| 0144 | 22 | | GA | | 1-5 | 33-16-41 | TB0071Y | A003 | BJ | | SM00004 | | W | | ALL |
| 0145 | 22 | | GA | | 1-2 | 33-16-41 | L00396 | 6 | 1A | | SM00004 | | W | | ALL |
| 0146 | 22 | | GA | | 1-3 | 33-16-41 | L00397 | 6 | 1A | | SM00004 | | W | | ALL |
| 0147 | 22 | | GA | | 1-3 | 33-16-41 | L00399 | 6 | 1A | | SM00004 | | W | | ALL |
| 0148 | 22 | | GA | | 1-2 | 33-16-41 | L00400 | 6 | 1A | | SM00004 | | W | | ALL |
| 0149 | 22 | | GA | | 1-4 | 33-16-41 | L00398 | 6 | 1A | | SM00004 | | W | | ALL |
| 0155 | 22 | | GA | | 3-11 | 34-46-11 | S10680 | 11 | 1A | | D40834J | 40 | | | 002 |
| 0169 | 20 | | GA | | 6-0 | 33-13-21 | S10680 | 15 | 1A | | D40834J | 43 | | | 002 |
| 0170 | 20 | | GA | | 6-0 | 33-13-21 | S10680 | 13 | 1A | | D40834J | 42 | | | 002 |
| 0171 | 22 | | GA | | 3-11 | 34-46-11 | S10680 | 12 | 1A | | D40834J | 41 | | | 002 |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE | | | | | | | | | | | |
| 0001 | 24 | | GK | | 6-2 | 34-12-62 | D40249P | 22 | | | TB0016Y | A016 | BJ | | ALL |
| 0002 | 24 | | GK | | 4-6 | 34-12-62 | D40073P | 18 | | | TB0016Y | A016 | BJ | | ALL |
| 0003 | 20 | | GA | | 6-10 | 34-12-62 | D40249P | 11 | | | GD01244 | DC.. | 2 | | ALL |
| 0004 | 24 | | GK | | 4-6 | 34-12-62 | D40073P | 14 | | | TB0016Y | A016 | BJ | | ALL |
| 0005 | 24 | | GK | | 6-2 | 34-13-21 | D40249P | 10 | | | TB0016Y | A008 | BJ | | ALL |
| 0006 | 20 | | GA | | 6-10 | 34-12-62 | D40249P | 5 | | | GD01244 | DC.. | 2 | | ALL |
| 0007 | 20 | | GA | | 6-10 | 34-12-62 | D40249P | 13 | | | GD01244 | DC.. | 2 | | ALL |
| 0009 | 24 | | GK | | 6-10 | 34-13-21 | D00287 | 8 | | | TB0016Y | A008 | BJ | | ALL |
| 0010 | 24 | | GK | | 8-2 | 34-13-21 | D00285 | 8 | | | TB0016Y | A008 | BJ | | ALL |
| 0011 | 24 | | GK | | 7-10 | 34-13-21 | D00285 | 3 | | | D40756P | 11 | | | ALL |
| 0012 | 20 | | GA | | 8-7 | 34-13-21 | D00285 | 4 | | | GD01243 | AC.. | 2 | | ALL |
| 0013 | 20 | | GA | | 8-7 | 34-13-21 | D00285 | 7 | | | GD01243 | ST.. | 2 | | ALL |
| 0014 | 20 | | GA | | 8-7 | 34-13-21 | D00285 | 10 | | | GD01243 | DC.. | 2 | | ALL |
| 0015 | 24 | | GK | | 6-7 | 34-13-21 | D00287 | 3 | | | D40756P | 12 | | | ALL |
| 0016 | 20 | | GA | | 7-4 | 34-13-21 | D00287 | 4 | | | GD01243 | AC.. | 2 | | ALL |
| 0017 | 20 | | GA | | 7-4 | 34-13-21 | D00287 | 10 | | | GD01243 | DC.. | 2 | | ALL |
| 0018 | 20 | | GA | | 7-4 | 34-13-21 | D00287 | 7 | | | GD01243 | ST.. | 2 | | ALL |
| 0019 | 24 | | GK | | 7-2 | 34-22-27 | D40525P | 31 | | | D40073P | 31 | | | ALL |
| 0020 | 20 | | GA | | 7-4 | 34-13-21 | D00287 | 38 | | | GD01243 | DC.. | 2 | | ALL |
| 0022 | 24 | | GK | | 9-8 | 27-58-11 | D02960 | 9 | | | D40035P | 55 | | | 001-099 |
| 0022 | 22 | | GA | | 9-8 | 27-58-11 | D02960 | 9 | | | D40035P | 55 | | | 115-199 |
| 0023 | 20 | | GA | | 6-10 | 34-22-37 | D40525P | 25 | | | GD01244 | DC.. | 2 | | ALL |
| 0024 | 24 | | GK | | 3-3 | 34-25-11 | D41041P | 26 | | | TB0016Y | C023 | BJ | | 001, 003-099, 115-199 |
| 0025 | 20 | | GA | | 8-9 | 34-22-91 | D00185 | 3 | | | GD01243 | DC.. | 2 | | 001-099 |
| 0025 | 20 | | GA | | 7-3 | 34-22-93 | D00801 | 3 | | | GD01243 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0026 | 20 | | GA | | 8-9 | 34-22-91 | D00185 | | 6 | | GD01243 | ST.. | 2 | | 001-099 |
| 0026 | 20 | | GA | | 7-3 | 34-22-93 | D00801 | | 6 | | GD01243 | ST.. | 2 | | 115-199 |
| 0027 | 24 | | GK | | 10-5 | 34-22-91 | D00185 | | 16 | | TB0014X | B002 | BJ | | 001-099 |
| 0027 | 24 | | GK | | 12-8 | 34-22-93 | D00801 | | 16 | | TB0014X | B002 | BJ | | 115-199 |
| 0028 | 20 | | GA | | 8-9 | 34-22-91 | D00185 | | 28 | | GD01243 | ST.. | 2 | | 001-099 |
| 0029 | 22 | | GA | | 6-5 | 34-22-92 | D00189 | | 3 | | D40756P | | 5 | | ALL |
| 0030 | 20 | | GA | | 7-1 | 34-22-92 | D00189 | | 4 | | GD01246 | AC.. | 2 | | ALL |
| 0031 | 20 | | GA | | 7-1 | 34-22-92 | D00189 | | 7 | | GD01246 | ST.. | 2 | | ALL |
| 0032 | 20 | | GA | | 7-1 | 34-22-92 | D00189 | | 10 | | GD01246 | DC.. | 2 | | ALL |
| 0033 | 24 | | GK | | 3-10 | 34-22-92 | D00189 | | 8 | | D40525P | | 21 | | ALL |
| 0034 | 20 | | GA | | 6-7 | 34-22-92 | D40525P | | 22 | | GD01246 | DC.. | 2 | | ALL |
| 0035 | 22 | | GA | | 11-9 | 34-32-11 | D40525P | | 13 | | TB0013Y | A003 | BJ | | ALL |
| 0036 | 22 | | GA | | 11-9 | 34-32-11 | D40525P | | 14 | | TB0013Y | C003 | BJ | | ALL |
| 0037 | 22 | | GA | | 11-9 | 34-32-11 | D40525P | | 15 | | TB0013Y | A004 | BJ | | ALL |
| 0038 | 24 | | GK | | 9-8 | 27-58-11 | D02960 | | 10 | | D40035P | | 54 | | 001-099 |
| 0038 | 22 | | GA | | 9-8 | 27-58-11 | D02960 | | 10 | | D40035P | | 54 | | 115-199 |
| 0039 | 24 | | GK | | 9-8 | 27-58-11 | D02960 | | 7 | | D40035P | | 53 | | 001-099 |
| 0039 | 22 | | GA | | 9-8 | 27-58-11 | D02960 | | 7 | | D40035P | | 53 | | 115-199 |
| 0040 | 24 | | GK | | 9-8 | 27-58-11 | D02960 | | 8 | | D40035P | | 52 | | 001-099 |
| 0040 | 22 | | GA | | 9-8 | 27-58-11 | D02960 | | 8 | | D40035P | | 52 | | 115-199 |
| 0041 | 24 | | GK | | 6-2 | 34-21-31 | D40525P | | 27 | | TB0016X | C009 | BJ | | ALL |
| 0045 | 22 | | GA | | 10-0 | 32-61-12 | D40836P | | 21 | | D40099P | | 48 | | ALL |
| 0046 | 22 | | GA | | 10-0 | 32-61-12 | D40836P | | 22 | | D40099P | | 49 | | ALL |
| 0047 | 24 | | GK | | 9-3 | 32-61-12 | D02372 | | 6 | | D40035P | | 35 | | 001-099 |
| 0047 | 22 | | GA | | 9-3 | 32-61-12 | D02372 | | 6 | | D40035P | | 35 | | 115-199 |
| 0048 | 24 | | GK | | 9-7 | 32-61-12 | D02372 | | 9 | | D40099P | | 50 | | 001-099 |
| 0048 | 22 | | GA | | 9-7 | 32-61-12 | D02372 | | 9 | | D40099P | | 50 | | 115-199 |
| 0049 | 20 | | GA | | 6-10 | 34-22-26 | D40525P | | 35 | | GD01244 | DC.. | 2 | | ALL |
| 0050 | 22 | | GA | | 7-2 | 34-22-26 | D40073P | | 7 | | D40525P | | 34 | | 001-099 |
| 0050 | 24 | | GK | | 7-2 | 34-22-26 | D40073P | | 7 | | D40525P | | 34 | | 115-199 |
| 0051 | 24 | | GK | | 7-2 | 34-22-27 | D40525P | | 16 | | D40073P | | 41 | | ALL |
| 0053 | 24 | | GK | | 4-6 | 34-22-27 | D40073P | | 33 | | TB0016Y | C023 | BJ | | ALL |
| 0054 | 22 | | GA | | 3-8 | 32-31-11 | D02372 | | 3 | | D40834P | | 24 | | ALL |
| 0055 | 22 | | GA | | 3-8 | 32-31-11 | D02372 | | 4 | | D40834P | | 25 | | ALL |
| 0056 | 24 | | GK | | 9-1 | 27-58-11 | D02960 | | 6 | | TB0016X | A021 | BJ | | 001-099 |
| 0056 | 22 | | GA | | 9-1 | 27-58-11 | D02960 | | 6 | | TB0016X | A021 | BJ | | 115-199 |
| 0057 | 24 | | GK | | 8-8 | 33-42-12 | D02372 | | 5 | | TB0015Y | C007 | BJ | | 001-099 |
| 0057 | 20 | | GA | | 8-8 | 33-42-12 | D02372 | | 5 | | TB0015Y | C007 | BJ | | 115-199 |
| 0058 | 24 | | GK | | 6-2 | 34-22-27 | D40525P | | 29 | | TB0016Y | C008 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 22

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|---------------|------------------------|-------------------------|
| Wire No. | GA CO TY | Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice |
| W0003 | 286N0003 | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | |
| 0059 | 24 | GK | 9-1 27-58-11 | D02960 3 | TB0016X B021 BJ 001-099 |
| 0059 | 22 | GA | 9-1 27-58-11 | D02960 3 | TB0016X B021 BJ 115-199 |
| 0060 | 24 | GK | 9-5 34-22-25 | D40854P 35 | TB0016X A005 BJ ALL |
| 0061 | 24 | GK | 9-5 34-22-25 | D40854P 36 | TB0016X B005 BJ ALL |
| 0062 | 24 | GK | 9-5 34-22-25 | D40854P 37 | TB0016X C005 BJ ALL |
| 0063 | 20 | GA | 9-5 27-51-61 | D40834P 21 | GD01245 DC.. 2 ALL |
| 0064 | 24 | GK | 8-10 27-51-61 | D40834P 13 | D42165P 40 ALL |
| 0065 | 24 | GK | 8-10 27-51-61 | D40834P 14 | D42165P 41 ALL |
| 0066 | 24 | GK | 8-10 27-51-61 | D40834P 15 | D42165P 42 ALL |
| 0067 | 20 | GA | 6-7 34-22-81 | D40525P 2 | GD01243 DC.. 2 001-099 |
| 0067 | 20 | GA | 6-7 34-22-83 | D40525P 2 | GD01243 DC.. 2 115-199 |
| 0068 | 24 | GK | 6-2 34-22-81 | D40525P 1 | TB0016Y C007 BJ 001-099 |
| 0068 | 24 | GK | 6-2 34-22-83 | D40525P 1 | TB0016Y C007 BJ 115-199 |
| 0069 | 24 | GK | 8-3 34-22-81 | D00185 29 | TB0016Z 11 BJ 001-099 |
| 0070 | 24 | GK | 10-5 34-22-81 | D00185 21 | TB0013Z 27 BJ 001-099 |
| 0071 | 24 | GK | 8-10 27-51-61 | D40834P 16 | D42165P 43 ALL |
| 0072 | 24 | GK | 8-10 27-51-61 | D40834P 17 | D42165P 44 ALL |
| 0073 | 24 | GK | 10-1 34-46-11 | D40836P 30 | D40073P 42 ALL |
| 0074 | 24 | GK | 10-1 34-46-11 | D40836P 32 | D40073P 43 ALL |
| 0075 | 24 | GK | 8-10 27-51-61 | D40834P 18 | D42165P 45 ALL |
| 0076 | 18 | GA | 9-7 30-42-11 | D41172P 21 | D01826 3 ALL |
| 0077 | 16 | GA | 9-11 30-42-11 | D40756P 23 | D01826 1 ALL |
| 0078 | 18 | GA | 9-7 30-42-11 | D41172P 23 | D01826 2 ALL |
| 0080 | 22 | GA | 3-2 33-16-11 | D41170P 3 | TB0015Y C023 BJ ALL |
| 0082 | 22 | GA | 6-2 33-16-11 | D40525P 5 | TB0015Z 3 BJ 001-099 |
| 0082 | 22 | GA | 6-2 33-16-51 | D40525P 5 | TB0015Z 3 BJ 115-199 |
| 0083 | 22 | GA | 6-10 33-16-11 | D00287 9 | TB0015Y C023 BJ ALL |
| 0084 | 24 | GK | 12-8 34-13-21 | D00287 12 | TB0014Y A009 BJ ALL |
| 0085 | 20 | GA | 2-0 34-22-92 | D40073P | GD01246 ST.. 2 ALL |
| 0088 | 24 | GK | 8-10 27-51-61 | D40834P 19 | D42165P 46 ALL |
| 0091 | 22 | GA | 3-2 33-16-21 | D41170P 9 | TB0015Y A024 BJ ALL |
| 0092 | 22 | GA | 6-10 33-16-21 | D00287 11 | TB0015Y A024 BJ ALL |
| 0093 | 22 | GA | 6-2 33-16-61 | D40525P 6 | TB0015Y A023 BJ ALL |
| 0094 | 24 | GK | 8-10 27-51-61 | D40834P 20 | D42165P 47 ALL |
| 0095 | 22 | GA | 8-7 33-16-31 | D41172P 9 | D40834P 10 ALL |
| 0097 | 24 | GK | 9-9 27-51-41 | D40836P 17 | D40035P 20 ALL |
| 0098 | 22 | GA | 3-1 33-16-61 | TB0015Y A023 BJ | D41174P 12 ALL |
| 0099 | 22 | GA | 9-2 33-16-41 | D40834P 12 | TB0015Z 14 BJ ALL |
| 0107 | 24 | GK | 3-3 33-14-11 | D40756P 6 | TB0015Y A016 BJ ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 23

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0108 | 24 | | GK | | 9-5 | 33-14-11 | D40854P | 18 | | | TB0015Y | A016 | BJ | | ALL |
| 0109 | 22 | | GA | | 9-0 | 33-14-11 | D40854P | 19 | | | D41174P | 30 | | | 001-099 |
| 0109 | 22 | | GA | | 9-2 | 33-14-11 | D40854P | 19 | | | D40756P | 14 | | | 115-199 |
| 0110 | 24 | | GK | | 3-4 | 33-13-21 | D40756P | 10 | | | D02888 | 12 | | | ALL |
| 0111 | 20 | | GA | | 4-7 | 33-13-21 | D02888 | 11 | | | GD01244 | AC.. | 2 | | ALL |
| 0112 | 20 | | GA | | 3-0 | 33-13-21 | D41172P | 1 | | | D02888 | 2 | | | ALL |
| 0113 | 20 | | GA | | 6-8 | 33-13-21 | SM00003 | | W | | D02888 | 9 | | | 001-099 |
| 0113 | 20 | | GA | | 6-8 | 33-13-21 | D02888 | 9 | | | SM00003 | | W | | 115-199 |
| 0114 | 20 | | GA | | 3-2 | 33-13-21 | D40249P | 9 | | | SM00007 | | W | | ALL |
| 0115 | 20 | | GA | | 3-2 | 33-13-21 | D40249P | 8 | | | SM00003 | | W | | ALL |
| 0116 | 20 | | GA | | 7-0 | 33-13-21 | GD01244 | AC.. | 2 | | SM00007 | | W | | ALL |
| 0117 | 20 | | GA | | 7-0 | 33-13-21 | GD01244 | AC.. | 2 | | SM00008 | | W | | ALL |
| 0118 | 20 | | GA | | 6-8 | 33-13-21 | D02888 | 8 | | | SM00009 | | W | | ALL |
| 0119 | 20 | | GA | | 4-7 | 33-13-21 | D02888 | 7 | | | GD01244 | ST.. | 2 | | ALL |
| 0120 | 24 | | GK | | 9-9 | 27-51-41 | D40836P | 18 | | | D40035P | 21 | | | ALL |
| 0121 | 22 | | GA | | 8-6 | 27-51-21 | D40836P | 29 | | | D41172P | 18 | | | ALL |
| 0122 | 22 | | GA | | 8-6 | 27-51-21 | D40836P | 1 | | | D41172P | 34 | | | ALL |
| 0123 | 22 | | GA | | 10-0 | 27-51-21 | D40836P | 2 | | | D40099P | 16 | | | ALL |
| 0124 | 22 | | GA | | 8-6 | 27-51-21 | D40836P | 3 | | | D41172P | 35 | | | ALL |
| 0125 | 22 | | GA | | 10-0 | 27-51-21 | D40836P | 4 | | | D40099P | 17 | | | ALL |
| 0126 | 22 | | GA | | 10-0 | 27-51-21 | D40836P | 5 | | | D40099P | 15 | | | 001-099 |
| 0126 | 22 | | GA | | 10-0 | SPARE | D40836P | 5 | | | D40099P | 15 | | | 115-199 |
| 0127 | 24 | | GK | | 8-11 | 27-51-11 | D40834P | 1 | | | D41041P | 7 | | | ALL |
| 0128 | 24 | | GK | | 8-11 | 27-51-11 | D40834P | 2 | | | D41041P | 8 | | | ALL |
| 0129 | 24 | | GK | | 8-11 | 27-51-11 | D40834P | 3 | | | D41041P | 9 | | | ALL |
| 0130 | 24 | | GK | | 8-11 | 27-51-11 | D40834P | 4 | | | D41041P | 10 | | | ALL |
| 0131 | 24 | | GK | | 8-11 | 27-51-11 | D40834P | 5 | | | D41041P | 11 | | | ALL |
| 0132 | 24 | | GK | | 8-11 | 27-51-11 | D40834P | 6 | | | D41041P | 12 | | | ALL |
| 0133 | 24 | | GK | | 8-11 | 27-51-11 | D40834P | 7 | | | D41041P | 13 | | | 115-199 |
| 0134 | 24 | | GK | | 8-11 | 27-51-11 | D40834P | 8 | | | D41041P | 14 | | | ALL |
| 0135 | 20 | | GA | | 4-0 | 33-13-41 | D40854P | 1 | | | SP00209 | | 9 | | ALL |
| 0136 | 20 | | GA | | 10-2 | 33-13-41 | D40854P | 2 | | | GD01244 | AC.. | 2 | | ALL |
| 0137 | 20 | | GA | | 5-5 | 33-13-41 | D02922 | 9 | | | SP00209 | | 9 | | ALL |
| 0138 | 20 | | GA | | 3-4 | 33-13-41 | D02922 | 2 | | | SP00213 | | W | | ALL |
| 0139 | 20 | | GA | | 3-4 | 33-13-41 | D02922 | 8 | | | SP00215 | | W | | ALL |
| 0140 | 24 | | GK | | 6-8 | 33-13-41 | D02922 | 12 | | | SM00010 | | W | | ALL |
| 0141 | 20 | | GA | | 11-6 | 33-13-41 | D02922 | 11 | | | GD01244 | AC.. | 2 | | ALL |
| 0142 | 20 | | GA | | 11-6 | 33-13-41 | D02922 | 7 | | | GD01244 | ST.. | 2 | | ALL |
| 0144 | 22 | | GA | | 2-11 | 33-16-41 | D41172P | 13 | | | TB0015Y | C012 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 24

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W0000
Page 25
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|-------|-----|--|----------|---------|---------|------|--------|-------|---------|------|-------------|--------|---------|
| | GA | CO TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0184 | 20 | GA | | 3-7 | 33-13-21 | | D00487 | | 3 | | SM00009 | | W | | ALL |
| 0185 | 22 | GA | | 5-4 | 22-41-13 | | D40249P | | 17 | | D42165P | 3 | | | ALL |
| 0186 | 22 | GA | | 6-9 | 22-41-13 | | D40249P | | 16 | | D40035P | 19 | | | ALL |
| 0187 | 20 | GA | | 6-5 | 22-41-13 | | D40249P | | 19 | | GD01241 | DC.. | 2 | | ALL |
| 0188 | 20 | GA | | 6-7 | 34-22-27 | | D40525P | | 17 | | GD01243 | DC.. | 2 | | ALL |
| 0189 | 24 | GK | | 11-9 | 34-22-37 | | D40525P | | 19 | | TB0013X | A001 | BJ | | ALL |
| 0191 | 18 | GA | | 10-5 | 30-42-11 | | D01826 | | 5 | | GD01245 | ST.. | 2 | | ALL |
| 0194 | 16 | GA | | 10-5 | 30-42-11 | | D01826 | | 6 | | GD01245 | DC.. | 2 | | ALL |
| 0196 | 20 | GA | | 3-7 | 33-13-21 | | D00487 | | 13 | | SM00008 | | W | | ALL |
| 0197 | 20 | GA | | 4-10 | 33-13-21 | | D40834P | | 27 | | SP00207 | | W | | ALL |
| 0198 | 20 | GA | | 4-6 | 33-13-21 | | D40834P | | 28 | | SM00008 | | W | | ALL |
| 0199 | 20 | GA | | 9-5 | 34-46-11 | | D40836P | | 26 | | GD01245 | AC.. | 2 | | ALL |
| 0200 | 20 | GA | | 9-5 | 34-46-11 | | D40836P | | 27 | | GD01245 | AC.. | 2 | | ALL |
| 0201 | 20 | GA | | 2-10 | 22-31-12 | | D00397 | | 31 | | GD01001 | ST.. | E | | ALL |
| 0203 | 20 | GA | | 4-8 | 33-13-21 | | D00397 | | 1 | | SP00207 | | W | | ALL |
| 0204 | 20 | GA | | 4-4 | 33-13-21 | | D00397 | | 2 | | SM00008 | | W | | ALL |
| 0205 | 20 | GA | | 9-5 | 27-51-21 | | D40836P | | 24 | | GD01245 | DC.. | 2 | | ALL |
| 0206 | 20 | GA | | 8-11 | 32-61-12 | | D02372 | | 7 | | GD01245 | DC.. | 2 | | ALL |
| 0208 | 22 | GA | | 9-4 | 27-58-11 | | D02960 | | 4 | | GD01245 | AC.. | 2 | | ALL |
| 0209 | 22 | GA | | 9-4 | 27-58-11 | | D02960 | | 5 | | GD01245 | AC.. | 2 | | ALL |
| 0210 | 22 | GA | | 9-4 | 27-58-11 | | D02960 | | 12 | | GD01245 | ST.. | 2 | | ALL |
| 0211 | 22 | GA | | 8-0 | 30-43-11 | | D41172P | | 17 | | D01824 | 1 | | | ALL |
| 0212 | 20 | GA | | 8-10 | 30-43-11 | | D01824 | | 3 | | GD01245 | DC.. | 2 | | ALL |
| 0213 | 20 | GA | | 8-10 | 30-43-11 | | D01824 | | 2 | | GD01245 | ST.. | 2 | | ALL |
| 0214 | 22 | GA | | 9-2 | 31-51-21 | | D40854P | | 27 | | D41041P | 48 | | | ALL |
| 0215 | 22 | GA | | 10-3 | 31-51-21 | | D40854P | | 26 | | TB0013Y | C004 | BJ | | ALL |
| 0216 | 20 | GA | | 9-10 | 31-51-21 | | D40854P | | 28 | | GD01246 | DC.. | 2 | | ALL |
| 0220 | 22 | GA | | 8-11 | 32-61-21 | | D40836P | | 50 | | D41041P | 20 | | | ALL |
| 0221 | 22 | GA | | 8-6 | 32-61-21 | | D40836P | | 51 | | D41172P | 5 | | | ALL |
| 0222 | 22 | GA | | 8-11 | 32-61-21 | | D40836P | | 52 | | D41041P | 22 | | | ALL |
| 0223 | 20 | GA | | 9-9 | SPARE | | D42174P | | 7 | | GD01248 | DC.. | 2 | | 001-099 |
| 0225 | 24 | GK | | 3-2 | 34-22-81 | | D41170P | | 11 | | TB0016Y | C007 | BJ | | 001-099 |
| 0225 | 24 | GK | | 3-2 | 34-22-83 | | D41170P | | 11 | | TB0016Y | C007 | BJ | | 115-199 |
| 0226 | 22 | GA | | 9-1 | 33-16-51 | | D40836P | | 55 | | TB0015Y | C015 | BJ | | ALL |
| 0227 | 22 | GA | | 9-2 | 33-16-61 | | D40834P | | 11 | | TB0015Y | A023 | BJ | | ALL |
| 0233 | 22 | GA | | 3-3 | 34-25-12 | | D42055P | | 8 | | TB0016Y | A018 | BJ | | 002 |
| 0234 | 22 | GA | | 5-0 | 34-25-12 | | D42165P | | 12 | | TB0016Y | A018 | BJ | | 002 |
| 0248 | 24 | GK | | 7-2 | 33-11-11 | | D00892 | | 16 | | SM00002 | | W | | ALL |
| 0249 | 24 | GK | | 5-3 | 33-11-11 | | D41172P | | 2 | | SM00002 | | W | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 26

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0250 | 20 | GA | | | 11-9 | 33-11-11 | D00892 | | 17 | | GD01246 | AC.. | 2 | | ALL |
| 0251 | 20 | GA | | | 11-9 | 33-11-11 | D00892 | | 21 | | GD01246 | ST.. | 2 | | ALL |
| 0252 | 20 | GA | | | 9-10 | 33-11-11 | D40854P | | 10 | | GD01246 | ST.. | 2 | | ALL |
| 0254 | 20 | GA | | | 9-1 | 32-61-12 | D02372 | | 11 | | GD01246 | DC.. | 2 | | ALL |
| 0255 | 22 | GA | | | 9-3 | 32-61-12 | D02372 | | 13 | | D40035P | | 34 | | 001-099 |
| 0255 | 22 | GA | | | 9-3 | 32-61-12 | D02372 | | 13 | | D40035P | | 36 | | 115-199 |
| 0256 | 22 | GA | | | 9-3 | 32-61-12 | D02372 | | 14 | | D40035P | | 39 | | ALL |
| 0257 | 22 | GA | | | 10-3 | 33-14-21 | D40854P | | 21 | | TB0013Y | A012 | BJ | | ALL |
| 0258 | 24 | GK | | | 9-7 | 32-61-12 | D02372 | | 8 | | D40099P | | 51 | | ALL |
| 0260 | 20 | GA | | | 4-1 | 33-13-21 | D00465 | | 1 | | SM00003 | | W | | 001-099 |
| 0260 | 20 | GA | | | 3-9 | 33-13-21 | D00465 | | 1 | | SM00003 | | W | | 115-199 |
| 0261 | 20 | GA | | | 4-1 | 33-13-21 | D00465 | | 2 | | SM00007 | | W | | 001-099 |
| 0261 | 20 | GA | | | 3-9 | 33-13-21 | D00465 | | 2 | | SM00007 | | W | | 115-199 |
| 0262 | 20 | GA | | | 4-2 | 33-13-21 | D00287 | | 1 | | SM00003 | | W | | ALL |
| 0263 | 20 | GA | | | 4-2 | 33-13-21 | D00287 | | 2 | | SM00007 | | W | | ALL |
| 0264 | 20 | GA | | | 4-0 | 33-13-21 | D00189 | | 1 | | SM00003 | | W | | ALL |
| 0265 | 20 | GA | | | 4-0 | 33-13-21 | D00189 | | 2 | | SM00007 | | W | | ALL |
| 0266 | 24 | GK | | | 3-3 | 34-22-26 | D40756P | | 3 | | TB0016X | A002 | BJ | | ALL |
| 0267 | 24 | GK | | | 3-3 | 34-22-26 | D40756P | | 4 | | TB0016X | B002 | BJ | | ALL |
| 0270 | 20 | GA | | | 9-0 | 32-41-11 | D00534 | | 5 | | GD01247 | ST.. | 2 | | ALL |
| 0272 | 22 | GA | | | 2-11 | 33-16-41 | D41172P | | 19 | | TB0015X | D022 | BJ | | ALL |
| 0273 | 22 | GA | | | 7-2 | 32-42-11 | D40249P | | 21 | | D40073P | | 32 | | ALL |
| 0274 | 22 | GA | | | 6-10 | 32-42-11 | D40249P | | 20 | | GD01248 | DC.. | 2 | | ALL |
| 0275 | 24 | GK | | | 2-11 | 33-42-12 | D41172P | | 14 | | TB0015Y | C007 | BJ | | 001-099 |
| 0275 | 22 | GA | | | 2-11 | 33-42-12 | D41172P | | 14 | | TB0015Y | C007 | BJ | | 115-199 |
| 0276 | 24 | GK | | | 4-1 | 32-61-12 | D40035P | | 40 | | TB0015Y | C007 | BJ | | 001-099 |
| 0276 | 22 | GA | | | 4-1 | 32-61-12 | D40035P | | 40 | | TB0015Y | C007 | BJ | | 115-199 |
| 0277 | 22 | GA | | | 3-3 | 34-61-25 | D40756P | | 9 | | TB0015X | D021 | BJ | | 001-099 |
| 0278 | 24 | GK | | | 8-10 | 27-51-61 | D40834P | | 35 | | D42165P | | 48 | | ALL |
| 0279 | 24 | GK | | | 8-10 | 27-51-61 | D40834P | | 36 | | D42165P | | 49 | | ALL |
| 0285 | 24 | GK | | | 8-11 | 27-51-11 | D40834P | | 33 | | D41041P | | 5 | | ALL |
| 0286 | 24 | GK | | | 8-11 | 27-51-11 | D40834P | | 34 | | D41041P | | 6 | | ALL |
| 0287 | 22 | GA | | | 8-6 | 27-51-21 | D40836P | | 10 | | D41172P | | 20 | | 001-099 |
| 0287 | 22 | GA | | | 8-6 | SPARE | D40836P | | 10 | | D41172P | | 20 | | 115-199 |
| 0292 | 20 | GA | | | 9-8 | 33-14-21 | D40854P | | 55 | | GD01241 | AC.. | 2 | | ALL |
| 0298 | 22 | GA | | | 7-0 | 34-25-12 | TB0016Y | A018 | BJ | | TB0016Y | C023 | BJ | | 002 |
| 0300 | 20 | GA | | | 3-4 | 33-11-21 | D03406 | | 2 | | SP00205 | | W | | ALL |
| 0302 | 20 | GA | | | 8-9 | 32-35-11 | D42174P | | 1 | | D42165P | | 5 | | ALL |
| 0303 | 24 | GK | | | 8-10 | 26-17-11 | D40836P | | 7 | | D42165P | | 1 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 27

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0304 | 24 | | GK | | 8-0 | 34-22-91 | D00185 | | 54 | | D40756P | | 2 | | 001-099 |
| 0305 | 20 | | GA | | 8-9 | 32-35-11 | D42174P | | 3 | | D42165P | | 7 | | ALL |
| 0306 | 20 | | GA | | 6-5 | 31-25-11 | D41174P | | 11 | | D00465 | | 8 | | 001-099 |
| 0306 | 20 | | GA | | 8-1 | 31-25-11 | D41174P | | 11 | | D00465 | | 8 | | 115-199 |
| 0307 | 20 | | GA | | 11-6 | 33-11-21 | D03406 | | 7 | | GD01244 | ST.. | 2 | | ALL |
| 0308 | 20 | | GA | | 7-1 | 31-25-11 | D00465 | | 9 | | GD01241 | DC.. | 2 | | 001-099 |
| 0308 | 20 | | GA | | 8-9 | 31-25-11 | D00465 | | 9 | | GD01241 | DC.. | 2 | | 115-199 |
| 0309 | 20 | | GA | | 3-1 | 34-22-83 | D41174P | | 4 | | TB0015X | A022 | BJ | | 115-199 |
| 0311 | 20 | | GA | | 11-6 | 33-11-21 | D03406 | | 11 | | GD01244 | AC.. | 2 | | ALL |
| 0312 | 24 | | GK | | 10-5 | 33-11-21 | D03406 | | 12 | | D41174P | | 32 | | ALL |
| 0313 | 20 | | GA | | 10-2 | 33-11-21 | D40854P | | 17 | | GD01244 | AC.. | 2 | | ALL |
| 0316 | 20 | | GA | | 5-1 | 33-11-21 | D40854P | | 16 | | SP00205 | | W | | ALL |
| 0318 | 22 | | GA | | 9-5 | 33-16-61 | D40854P | | 22 | | TB0015Y | C024 | BJ | | ALL |
| 0324 | 22 | | GA | | 8-4 | 22-14-21 | D00403 | | 1 | | TB0016Y | C016 | BJ | | ALL |
| 0326 | 22 | | GA | | 9-5 | 33-16-51 | D40854P | | 24 | | TB0015Z | | 3 | BJ | ALL |
| 0330 | 22 | | GA | | 3-1 | 33-16-51 | D41174P | | 17 | | TB0015Z | | 3 | BJ | ALL |
| 0331 | 22 | | GA | | 3-1 | 33-16-51 | D41174P | | 6 | | TB0015Z | | 4 | BJ | ALL |
| 0332 | 22 | | GA | | 3-2 | 22-14-21 | D42165P | | 2 | | TB0016Y | C016 | BJ | | ALL |
| 0333 | 20 | | GA | | 9-9 | 32-35-11 | D42174P | | 15 | | GD01248 | ST.. | 2 | | ALL |
| 0334 | 20 | | GA | | 8-9 | 32-35-11 | D42174P | | 2 | | D42165P | | 6 | | ALL |
| 0335 | 24 | | GK | | 4-9 | 33-11-11 | D40854P | | 41 | | SM00011 | | W | | ALL |
| 0337 | 24 | | GK | | 4-9 | 33-11-11 | D40854P | | 42 | | SM00002 | | W | | ALL |
| 0338 | 22 | | GA | | 3-1 | 33-16-61 | D41174P | | 9 | | TB0015Y | C024 | BJ | | ALL |
| 0342 | 24 | | GK | | 8-2 | 32-41-11 | D00534 | | 6 | | D42165P | | 8 | | ALL |
| 0343 | 24 | | GK | | 8-2 | 32-41-11 | D00534 | | 3 | | D42165P | | 9 | | ALL |
| 0344 | 24 | | GK | | 8-2 | 32-41-11 | D00534 | | 4 | | D42165P | | 11 | | ALL |
| 0345 | 20 | | GA | | 8-9 | 34-22-91 | D00185 | | 55 | | GD01243 | AC.. | 2 | | 001-099 |
| 0346 | 22 | | GA | | 9-1 | 33-16-51 | D40836P | | 12 | | TB0015Z | | 3 | BJ | 115-199 |
| 0347 | 22 | | GA | | 9-1 | 33-16-51 | D40836P | | 11 | | TB0015Z | | 4 | BJ | 115-199 |
| 0370 | 22 | | GA | | 9-1 | 33-16-51 | D40836P | | 13 | | TB0015Z | | 3 | BJ | ALL |
| 0371 | 24 | | GK | | 3-2 | 32-41-11 | D42165P | | 10 | | TB0015X | B022 | BJ | | ALL |
| 0372 | 20 | | GA | | 8-9 | 32-35-11 | D42174P | | 4 | | D42165P | | 16 | | 115-199 |
| 0373 | 22 | | GA | | 9-1 | 33-16-51 | D42174P | | 5 | | TB0015Y | A015 | BJ | | 115-199 |
| 0374 | 22 | | GA | | 9-1 | 33-16-51 | D42174P | | 6 | | TB0015Y | A017 | BJ | | 115-199 |
| 0376 | 24 | | GK | | 10-10 | 33-11-11 | D05242 | | A3 | | D41174P | | 5 | | ALL |
| 0377 | 24 | | GK | | 5-5 | 33-11-11 | SM00011 | | | W | D41174P | | 1 | | 001-099 |
| 0377 | 24 | | GK | | 5-5 | 33-11-11 | D41174P | | 1 | | SM00011 | | W | | 115-199 |
| 0378 | 24 | | GK | | 7-1 | 33-11-11 | D05242 | | A2 | | SM00011 | | W | | ALL |
| 0379 | 24 | | GK | | 7-1 | 33-11-11 | D05242 | | X1 | | SM00012 | | W | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 28

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0380 | 20 | GA | | | 11-8 | 33-11-11 | D05242 | X2 | | | GD01246 | ST.. | 2 | | ALL |
| 0381 | 24 | GK | | | 6-0 | 33-11-11 | D41170P | 5 | | | SM00012 | | W | | ALL |
| 0382 | 24 | GK | | | 7-1 | 33-11-11 | D05242 | A1 | | | SM00012 | | W | | ALL |
| 0383 | 22 | GA | | | 9-1 | 33-16-51 | D40836P | 8 | | | TB0015Z | 3 | BJ | | ALL |
| 0384 | 22 | GA | | | 9-1 | 33-16-51 | D40836P | 9 | | | TB0015Z | 4 | BJ | | ALL |
| 0395 | 22 | GA | | | 5-0 | 34-22-28 | TB0016Y | | C023 | BJ | D40073P | 51 | | | 002 |
| 0396 | 22 | GA | | | 14-0 | 34-46-11 | D40834P | 40 | | | D40073P | 34 | | | 002 |
| 0400 | 22 | PA | | | 6-5 | 34-61-18 | D40525P | 36 | | | GD01247 | DC.. | 2 | | 115-199 |
| 0401 | 22 | PA | | | 6-5 | 34-61-18 | D40525P | 37 | | | GD01247 | DC.. | 2 | | 115-199 |
| 0402 | 22 | PA | | | 5-5 | 34-61-18 | D40525P | 38 | | | D42055P | 13 | | | 115-199 |
| 0403 | 22 | PA | | | 6-5 | 34-61-18 | D40525P | 39 | | | GD01247 | DC.. | 2 | | 115-199 |
| 0404 | 22 | PA | | | 6-5 | 34-61-18 | D40525P | 40 | | | GD01247 | DC.. | 2 | | 115-199 |
| 0405 | 22 | PA | | | 7-1 | 34-61-18 | D40525P | 41 | | | D40099P | 47 | | | 115-199 |
| 0416 | 22 | GA | | | 12-0 | 34-12-62 | D40249P | 14 | | | D41041P | 1 | | | 001-099 |
| 0416 | 22 | GA | | | 12-0 | 34-12-62 | D41041P | 1 | | | D40249P | 14 | | | 115-199 |
| 0417 | 22 | GA | | | 12-0 | 34-12-62 | D40249P | 15 | | | D41041P | 2 | | | 001-099 |
| 0417 | 22 | GA | | | 12-0 | 34-12-62 | D41041P | 2 | | | D40249P | 15 | | | 115-199 |
| 0418 | 22 | GA | | | 7-6 | 34-12-62 | D40249P | 12 | | | TB0013X | A020 | BJ | | 001-099 |
| 0418 | 22 | GA | | | 7-6 | 34-12-62 | TB0013X | A020 | BJ | | D40249P | 12 | | | 115-199 |
| 0421 | 20 | GA | | | 7-1 | 31-25-11 | D00465 | 7 | | | GD01241 | DC.. | 2 | | 001-099 |
| 0421 | 20 | GA | | | 8-9 | 31-25-11 | D00465 | 7 | | | GD01241 | DC.. | 2 | | 115-199 |
| 0424 | 20 | GA | | | 7-1 | 31-25-11 | D00465 | 4 | | | GD01241 | DC.. | 2 | | 001-099 |
| 0424 | 20 | GA | | | 8-9 | 31-25-11 | D00465 | 4 | | | GD01241 | DC.. | 2 | | 115-199 |
| 0437 | 20 | GA | | | 4-10 | 33-13-21 | D40834P | 29 | | | SP00207 | | W | | ALL |
| 0440 | 20 | GA | | | 2-0 | 31-25-11 | D40099P | | | AC | GD01242 | ST.. | 2 | | ALL |
| 0441 | 20 | GA | | | 2-0 | 22-32-11 | D40035P | | | AD | GD01245 | ST.. | 2 | | ALL |
| 0442 | 22 | GA | | | 9-5 | 31-41-14 | D40854P | 29 | | | TB0015Y | C005 | BJ | | ALL |
| 0443 | 22 | GA | | | 4-1 | 31-41-14 | D40035P | 32 | | | TB0015Y | C005 | BJ | | ALL |
| 0445 | 22 | GA | | | 4-1 | 31-41-14 | D40035P | 31 | | | TB0015Y | A005 | BJ | | ALL |
| 0448 | 22 | GA | | | 9-5 | 31-41-14 | D40854P | 48 | | | TB0015Y | A005 | BJ | | ALL |
| 0449 | 20 | GA | | | 10-1 | 31-41-14 | D40854P | 49 | | | GD01248 | DC.. | 2 | | ALL |
| 0457 | 22 | GA | | | 0-7 | 22-14-21 | D00487 | 15 | | | D00487 | 4 | | | ALL |
| 0458 | 22 | GA | | | 0-9 | 22-14-21 | D00403 | 9 | | | SM00001 | | W | | ALL |
| 0459 | 22 | GA | | | 0-9 | 22-14-21 | D00403 | 8 | | | SM00001 | | W | | ALL |
| 0460 | 22 | GA | | | 0-9 | 22-14-21 | D00403 | 2 | | | SM00001 | | W | | ALL |
| 0461 | 22 | GA | | | 9-5 | 33-16-41 | D40854P | 25 | | | TB0015Z | 14 | BJ | | ALL |
| 0462 | 22 | GA | | | 8-10 | 33-16-31 | D40854P | 23 | | | D41172P | 27 | | | ALL |
| 0481 | 24 | GK | | | 8-11 | 27-51-11 | D40834P | 22 | | | D41041P | 19 | | | ALL |
| 0482 | 22 | GA | | | 9-9 | 32-46-11 | D40836P | 15 | | | D40035P | 23 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 29

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|-------------|--------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W0003 | 286N0003 | | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0483 | 22 | | GA | | 3-3 | 32-42-12 | | D40756P | | 8 | | TB0016X | D002 | BJ | | 115-199 |
| 0484 | 20 | | GA | | 3-8 | 33-13-41 | | D05032 | | A3 | | SP00217 | | W | | ALL |
| 0485 | 20 | | GA | | 3-8 | 33-13-41 | | D05032 | | A1 | | SP00215 | | W | | ALL |
| 0486 | 24 | | GK | | 7-0 | 33-13-41 | | D05032 | | X1 | | SM00010 | | W | | ALL |
| 0487 | 20 | | GA | | 11-10 | 33-13-41 | | D05032 | | X2 | | GD01248 | AC.. | 2 | | ALL |
| 0488 | 20 | | GA | | 3-8 | 33-13-41 | | D05032 | | A2 | | SP00211 | | W | | ALL |
| 0490 | 22 | | GA | | 9-11 | 34-22-36 | | D40834P | | 38 | | TB0013X | A016 | BJ | | ALL |
| 0491 | 22 | | GA | | 9-11 | 34-22-36 | | D40834P | | 37 | | TB0013Y | A017 | BJ | | ALL |
| 0492 | 22 | | GA | | 10-5 | 34-22-36 | | D00185 | | 17 | | TB0013Y | C017 | BJ | | 001-099 |
| 0492 | 22 | | GA | | 12-8 | 34-22-36 | | D00801 | | 17 | | TB0013Y | C017 | BJ | | 115-199 |
| 0493 | 22 | | GA | | 9-11 | 34-22-36 | | D40834P | | 39 | | TB0013Y | C017 | BJ | | ALL |
| 0494 | 22 | | GA | | 15-4 | 34-22-26 | | D40073P | | 25 | | TB0013Y | C017 | BJ | | ALL |
| 0500 | 24 | | GK | | 6-2 | 34-22-27 | | D40525P | | 3 | | TB0015X | B021 | BJ | | 001-099 |
| 0500 | 24 | | GK | | 6-2 | 34-61-26 | | D40525P | | 3 | | TB0015X | B021 | BJ | | 115-199 |
| 0501 | 24 | | GK | | 3-1 | 34-22-93 | | D00801 | | 21 | | D00805 | | 7 | | 115-199 |
| 0502 | 24 | | GK | | 3-1 | 34-22-93 | | D00801 | | 14 | | D00805 | | 4 | | 115-199 |
| 0503 | 24 | | GK | | 3-1 | 34-22-93 | | D00801 | | 12 | | D00803 | | 7 | | 115-199 |
| 0504 | 24 | | GK | | 3-1 | 34-22-93 | | D00801 | | 10 | | D00803 | | 4 | | 115-199 |
| 0505 | 20 | | GA | | 7-3 | 34-22-93 | | D00803 | | 10 | | GD01243 | ST.. | 2 | | 115-199 |
| 0506 | 24 | | GK | | 12-8 | 34-22-93 | | D00803 | | 8 | | TB0014Y | C010 | BJ | | 115-199 |
| 0507 | 20 | | GA | | 7-4 | 34-22-93 | | D00803 | | 2 | | GD01247 | DC.. | 2 | | 115-199 |
| 0508 | 24 | | GK | | 6-3 | 34-22-93 | | D41172P | | 33 | | D00803 | | 1 | | 115-199 |
| 0509 | 24 | | GK | | 6-10 | 34-22-93 | | D00805 | | 8 | | TB0016Y | A023 | BJ | | 115-199 |
| 0510 | 20 | | GA | | 7-3 | 34-22-93 | | D00805 | | 10 | | GD01243 | ST.. | 2 | | 115-199 |
| 0511 | 24 | | GK | | 2-11 | 34-22-93 | | D41172P | | 30 | | TB0016Y | A023 | BJ | | 115-199 |
| 0512 | 20 | | GA | | 3-3 | 29-21-32 | | D40756P | | 19 | | TB0015X | C022 | BJ | | ALL |
| 0513 | 24 | | GK | | 6-3 | 34-22-93 | | D00801 | | 54 | | D41172P | | 32 | | 115-199 |
| 0514 | 20 | | GA | | 7-4 | 34-22-93 | | D00801 | | 55 | | GD01247 | AC.. | 2 | | 115-199 |
| 0547 | 20 | | GA | | 14-0 | 34-46-11 | | GD01245 | AC.. | 2 | | D40834P | | 41 | | 002 |
| 0550 | 24 | | GK | | 8-3 | 34-55-21 | | D00813 | | 9 | | TB0016Z | 11 | BJ | | 115-199 |
| 0551 | 22 | | GA | | 3-7 | 34-55-21 | | D00811 | | 1 | | SM00030 | | W | | 115-199 |
| 0552 | 20 | | GA | | 8-11 | 34-55-21 | | D00811 | | 2 | | GD01248 | AC.. | 2 | | 115-199 |
| 0553 | 20 | | GA | | 8-11 | 34-55-21 | | D00813 | | 10 | | GD01248 | ST.. | 2 | | 115-199 |
| 0554 | 22 | | GA | | 5-3 | 34-55-21 | | D41172P | | 31 | | SM00030 | | W | | 115-199 |
| 0555 | 22 | | GA | | 6-1 | 34-55-21 | | D41041P | | 42 | | SM00030 | | W | | 115-199 |
| 0556 | 24 | | GK | | 8-0 | 34-55-21 | | D41041P | | 46 | | D00813 | 11 | | | 115-199 |
| 0557 | 24 | | GK | | 10-5 | 34-55-11 | | D00811 | | 9 | | TB0013Z | 27 | BJ | | 115-199 |
| 0558 | 24 | | GK | | 8-1 | 34-55-11 | | D00811 | | 11 | | D42055P | 16 | | | 115-199 |
| 0559 | 20 | | GA | | 4-1 | 33-13-21 | | D00805 | | 1 | | SM00003 | | W | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 30

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0560 | 20 | GA | | | 4-1 | 33-13-21 | D00805 | 2 | | | SM00007 | | W | | 115-199 | |
| 0561 | 20 | GA | | | 3-7 | 33-13-21 | D00813 | 1 | | | SM00009 | | W | | 115-199 | |
| 0562 | 20 | GA | | | 3-7 | 33-13-21 | D00813 | 2 | | | SM00008 | | W | | 115-199 | |
| 0563 | 20 | GA | | | 8-11 | 34-55-21 | D00813 | 3 | | | GD01248 | DC.. | 2 | | 115-199 | |
| 0564 | 24 | GK | | | 6-2 | 34-22-37 | D40525P | 24 | | | TB0016Y | C023 | BJ | | ALL | |
| 0565 | 24 | GK | | | 14-11 | 77-12-11 | D40035P | 22 | | | TB0013X | B001 | BJ | | 001-099 | |
| 0565 | 24 | GK | | | 14-2 | 77-12-11 | D42055P | 28 | | | TB0013X | B001 | BJ | | 115-199 | |
| 0567 | 24 | GK | | | 15-3 | 77-12-11 | D40099P | 25 | | | TB0013X | A005 | BJ | | 001-099 | |
| 0567 | 24 | GK | | | 14-1 | 77-12-11 | D41041P | 23 | | | TB0013X | A005 | BJ | | 115-199 | |
| 0569 | 22 | GA | | | 8-11 | 32-31-11 | D40756P | 13 | | | D40834P | 23 | | | ALL | |
| 0570 | 22 | GA | | | 8-11 | 32-31-11 | D41041P | 17 | | | D40834P | 26 | | | ALL | |
| 0600 | 22 | PA | | | 4-9 | 34-61-26 | D40525P | 4 | | | GD01247 | DC.. | 2 | | 115-199 | |
| 0601 | 22 | PA | | | 4-9 | 34-61-26 | D40525P | 12 | | | TB0015Y | A009 | BJ | | 115-199 | |
| 0602 | 22 | PA | | | 4-9 | 34-61-26 | D40525P | 20 | | | GD01247 | DC.. | 2 | | 115-199 | |
| 0603 | 22 | PA | | | 4-9 | 34-61-26 | TB0013Y | C017 | BJ | | TB0015X | A021 | BJ | | 115-199 | |
| 0604 | 20 | GA | | | 14-0 | 33-13-21 | GD01248 | AC.. | 2 | | D40834P | 43 | | | 002 | |
| 0605 | 20 | GA | | | 6-0 | 33-13-21 | SP00207 | | W | | D40834P | 42 | | | 002 | |
| 0700 | 22 | PA | | | 4-9 | 34-61-25 | TB0015Y | A010 | BJ | | D40073P | 36 | | | 115-199 | |
| 0701 | 22 | PA | | | 6-5 | 34-61-25 | D40525P | 30 | | | GD01247 | DC.. | 2 | | 115-199 | |
| 0702 | 22 | PA | | | 6-5 | 34-61-25 | D40525P | 32 | | | GD01247 | DC.. | 2 | | 115-199 | |
| 0703 | 22 | PA | | | 5-5 | 34-61-25 | D40525P | 26 | | | TB0015Y | A010 | BJ | | 115-199 | |
| 0704 | 22 | PA | | | 4-9 | 34-61-26 | TB0015Y | A009 | BJ | | D40073P | 35 | | | 115-199 | |
| 1002 | 20 | GT | DL | | 3-3 | 29-21-32 | D40756P | 18 | | | TB0015X | C021 | BJ | | ALL | |
| 1002Z | | | DL | | 0-0 | 29-21-32 | D40756P | DED | | | TB0015X | DED | | | ALL | |
| 2001B | 22 | GB | CA | | 7-5 | 34-12-11 | D00287 | 28 | | | D40035P | 28 | | | ALL | |
| 2001R | 22 | GB | CA | | 0-0 | 34-12-11 | D00287 | 27 | | | D40035P | 27 | | | ALL | |
| 2002B | 22 | GB | CC | | 7-10 | 34-12-21 | D00287 | 23 | | | D40073P | 23 | | | ALL | |
| 2002R | 22 | GB | CC | | 0-0 | 34-12-21 | D00287 | 22 | | | D40073P | 22 | | | ALL | |
| 2003B | 24 | GL | CX | | 8-10 | 22-31-12 | D00397 | 7 | | | D42055P | 18 | | | ALL | |
| 2003R | 24 | GL | CX | | 0-0 | 22-31-12 | D00397 | 8 | | | D42055P | 17 | | | ALL | |
| 2004B | 24 | GL | CY | | 8-10 | 22-31-12 | D00397 | 6 | | | D42055P | 20 | | | ALL | |
| 2004R | 24 | GL | CY | | 0-0 | 22-31-12 | D00397 | 5 | | | D42055P | 19 | | | ALL | |
| 2005B | 22 | GB | CZ | | 8-10 | 22-31-12 | D00397 | 4 | | | D42055P | 22 | | | ALL | |
| 2005R | 22 | GB | CZ | | 0-0 | 22-31-12 | D00397 | 3 | | | D42055P | 21 | | | ALL | |
| 2008B | 24 | GL | BC | | 7-3 | 33-11-11 | D00892 | 12 | | | D40854P | 44 | | | ALL | |
| 2008R | 24 | GL | BC | | 0-0 | 33-11-11 | D00892 | 13 | | | D40854P | 43 | | | ALL | |
| 2009B | 24 | GL | BD | | 7-3 | 33-11-11 | D00892 | 4 | | | D40854P | 4 | | | ALL | |
| 2009R | 24 | GL | BD | | 0-0 | 33-11-11 | D00892 | 5 | | | D40854P | 5 | | | ALL | |
| 2010B | 24 | GL | BE | | 7-3 | 33-11-11 | D00892 | 6 | | | D40854P | 6 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 31

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 2010R | 24 | GL | BE | 0-0 | 33-11-11 | D00892 | 7 | | | | D40854P | 7 | | | ALL |
| 2020B | 24 | PL | AX | 9-2 | 23-51-21 | D40854P | 30 | | | | D41170P | 30 | | | 115-199 |
| 2020R | 24 | PL | AX | 0-0 | 23-51-21 | D40854P | 31 | | | | D41170P | 31 | | | 115-199 |
| 2501B | 24 | G2 | AD | 9-5 | 34-22-25 | D40854P | 34 | | | | TB0016Z | 30 | BJ | | ALL |
| 2501R | 24 | G2 | AD | 0-0 | 34-22-25 | D40854P | 33 | | | | TB0016Z | 29 | BJ | | ALL |
| 2501Z | | | AD | 0-0 | 34-22-25 | D40854P | DED | | | | TB0016Z | 31 | BJ | | ALL |
| 2504B | 24 | G2 | DQ | 15-3 | 77-12-11 | D40099P | 53 | | | | TB0013X | D006 | BJ | | 001-099 |
| 2504R | 24 | G2 | DQ | 0-0 | 77-12-11 | D40099P | 52 | | | | TB0013X | C006 | BJ | | 001-099 |
| 2504Z | | | DQ | 0-0 | 77-12-11 | D40099P | 54 | | | | GD01019 | ST.. | 2 | | 001-099 |
| 2509B | 24 | G2 | DT | 14-11 | 77-12-11 | D40035P | 46 | | | | TB0013X | B006 | BJ | | 001-099 |
| 2509R | 24 | G2 | DT | 0-0 | 77-12-11 | D40035P | 45 | | | | TB0013X | A006 | BJ | | 001-099 |
| 2509Z | | | DT | 0-0 | 77-12-11 | D40035P | 47 | | | | GD01019 | ST.. | 2 | | 001-099 |
| 2515B | 24 | G2 | BA | 7-3 | 33-11-11 | D00892 | 9 | | | | D40854P | 9 | | | ALL |
| 2515R | 24 | G2 | BA | 0-0 | 33-11-11 | D00892 | 3 | | | | D40854P | 3 | | | ALL |
| 2515Z | | | BA | 0-0 | 33-11-11 | D00892 | | | AE | | D40854P | 8 | | | ALL |
| 2516B | 24 | G2 | BB | 10-10 | 33-11-11 | D00892 | 10 | | | | D41172P | 3 | | | ALL |
| 2516R | 24 | G2 | BB | 0-0 | 33-11-11 | D00892 | 1 | | | | D41172P | 4 | | | ALL |
| 2516Z | | | BB | 0-0 | 33-11-11 | D00892 | | | AE | | D41172P | 39 | | | ALL |
| 2517B | 24 | G2 | DM | 14-2 | 77-12-11 | D42055P | 30 | | | | TB0013X | C001 | BJ | | 115-199 |
| 2517R | 24 | G2 | DM | 0-0 | 77-12-11 | D42055P | 29 | | | | TB0013X | D001 | BJ | | 115-199 |
| 2517Z | | | DM | 0-0 | 77-12-11 | D42055P | 31 | | | | GD01017 | ST.. | 2 | | 115-199 |
| 2518B | 24 | G2 | DN | 14-1 | 77-12-11 | D41041P | 54 | | | | TB0013X | B005 | BJ | | 115-199 |
| 2518R | 24 | G2 | DN | 0-0 | 77-12-11 | D41041P | 53 | | | | TB0013X | C005 | BJ | | 115-199 |
| 2518Z | | | DN | 0-0 | 77-12-11 | D41041P | 55 | | | | GD01017 | ST.. | 2 | | 115-199 |
| 3001B | 24 | GM | CB | 7-5 | 34-12-11 | D00287 | 25 | | | | D40035P | 25 | | | ALL |
| 3001R | 24 | GM | CB | 0-0 | 34-12-11 | D00287 | 24 | | | | D40035P | 24 | | | ALL |
| 3001Y | 24 | GM | CB | 0-0 | 34-12-11 | D00287 | 26 | | | | D40035P | 26 | | | ALL |
| 3002B | 24 | GM | CD | 7-10 | 34-12-21 | D00287 | 20 | | | | D40073P | 20 | | | ALL |
| 3002R | 24 | GM | CD | 0-0 | 34-12-21 | D00287 | 19 | | | | D40073P | 19 | | | ALL |
| 3002Y | 24 | GM | CD | 0-0 | 34-12-21 | D00287 | 21 | | | | D40073P | 21 | | | ALL |
| 3003B | 24 | GM | AC | 10-6 | 33-13-41 | D02922 | 5 | | | | D41170P | 2 | | | 001-099 |
| 3003B | 24 | GM | AC | 10-6 | 33-13-41 | D41170P | 2 | | | | D02922 | 5 | | | 115-199 |
| 3003R | 24 | GM | AC | 0-0 | 33-13-41 | D02922 | 6 | | | | D41170P | 1 | | | 001-099 |
| 3003R | 24 | GM | AC | 0-0 | 33-13-41 | D41170P | 1 | | | | D02922 | 6 | | | 115-199 |
| 3003Y | 24 | GM | AC | 0-0 | 33-13-41 | D02922 | 1 | | | | D41170P | 7 | | | 001-099 |
| 3003Y | 24 | GM | AC | 0-0 | 33-13-41 | D41170P | 7 | | | | D02922 | 1 | | | 115-199 |
| 3004B | 24 | GM | AA | 10-5 | 33-11-21 | D03406 | 6 | | | | D41174P | 19 | | | ALL |
| 3004R | 24 | GM | AA | 0-0 | 33-11-21 | D03406 | 5 | | | | D41174P | 18 | | | ALL |
| 3004Y | 24 | GM | AA | 0-0 | 33-11-21 | D03406 | 1 | | | | D41174P | 20 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 32

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | Effectivity | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|-------------|------|---------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 3006B | 24 | GM | AI | | 4-9 | 33-13-21 | D40854P | 14 | | | SM00005 | | W | | 115-199 |
| 3006R | 24 | GM | AI | | 0-0 | 33-13-21 | D40854P | 13 | | | SM00004 | | W | | 115-199 |
| 3006Y | 24 | GM | AI | | 0-0 | 33-13-21 | D40854P | 15 | | | SM00006 | | W | | 115-199 |
| 3007B | 24 | GM | AB | | 9-9 | 33-13-21 | D02888 | 5 | | | D40854P | 14 | | | 001-099 |
| 3007B | 24 | GM | AB | | 6-8 | 33-13-21 | D02888 | 5 | | | SM00005 | | W | | 115-199 |
| 3007R | 24 | GM | AB | | 0-0 | 33-13-21 | D02888 | 6 | | | D40854P | 13 | | | 001-099 |
| 3007R | 24 | GM | AB | | 0-0 | 33-13-21 | D02888 | 6 | | | SM00004 | | W | | 115-199 |
| 3007Y | 24 | GM | AB | | 0-0 | 33-13-21 | D02888 | 1 | | | D40854P | 15 | | | 001-099 |
| 3007Y | 24 | GM | AB | | 0-0 | 33-13-21 | D02888 | 1 | | | SM00006 | | W | | 115-199 |
| 3008B | 24 | GM | AJ | | 5-3 | 33-13-71 | D41172P | 24 | | | SM00005 | | W | | 115-199 |
| 3008R | 24 | GM | AJ | | 0-0 | 33-13-71 | D41172P | 25 | | | SM00004 | | W | | 115-199 |
| 3008Y | 24 | GM | AJ | | 0-0 | 33-13-71 | D41172P | 26 | | | SM00006 | | W | | 115-199 |
| 3013B | 24 | GM | AG | | 7-9 | 31-25-11 | D00465 | 14 | | | D40854P | 38 | | | 001-099 |
| 3013B | 24 | GM | AG | | 5-2 | 31-25-11 | D00465 | 14 | | | D40854P | 38 | | | 115-199 |
| 3013R | 24 | GM | AG | | 0-0 | 31-25-11 | D00465 | 13 | | | D40854P | 39 | | | ALL |
| 3013Y | 24 | GM | AG | | 0-0 | 31-25-11 | D00465 | 15 | | | D40854P | 40 | | | ALL |
| 3502B | 24 | G3 | CK | | 5-0 | 33-11-11 | D00892 | 18 | | | D05242 | B3 | | | ALL |
| 3502R | 24 | G3 | CK | | 0-0 | 33-11-11 | D00892 | 11 | | | D05242 | B2 | | | ALL |
| 3502Y | 24 | G3 | CK | | 0-0 | 33-11-11 | D00892 | 8 | | | D05242 | B1 | | | ALL |
| 3502Z | | | CK | | 0-0 | 33-11-11 | D00892 | | | AE | D05242 | DED | | | ALL |
| 4501G | 22 | DU | EA | | 14-2 | 77-21-11 | D42055P | 3 | | | TB0013X | A002 | BJ | | 001-099 |
| 4501G | 22 | DU | DO | | 14-2 | 77-21-11 | D42055P | 3 | TD | | TB0013X | A002 | BJ | | 115-199 |
| 4501W | 22 | DU | EA | | 0-0 | 77-21-11 | D42055P | 2 | | | TB0013X | B002 | BJ | | 001-099 |
| 4501W | 22 | DU | DO | | 0-0 | 77-21-11 | D42055P | 2 | TC | | TB0013X | B002 | BJ | | 115-199 |
| 4501Z | | | EA | | 0-0 | 77-21-11 | D42055P | 1 | | | GD01017 | ST.. | 2 | | 001-099 |
| 4501Z | | | DO | | 0-0 | 77-21-11 | D42055P | 1 | | | GD01017 | ST.. | 2 | | 115-199 |
| 4502G | 22 | DU | EB | | 14-1 | 77-21-11 | D41041P | 52 | | | TB0013X | C002 | BJ | | 001-099 |
| 4502G | 22 | DU | DP | | 14-1 | 77-21-11 | D41041P | 52 | TD | | TB0013X | C002 | BJ | | 115-199 |
| 4502W | 22 | DU | EB | | 0-0 | 77-21-11 | D41041P | 51 | | | TB0013X | D002 | BJ | | 001-099 |
| 4502W | 22 | DU | DP | | 0-0 | 77-21-11 | D41041P | 51 | TC | | TB0013X | D002 | BJ | | 115-199 |
| 4502Z | | | EB | | 0-0 | 77-21-11 | D41041P | 50 | | | GD01017 | ST.. | 2 | | 001-099 |
| 4502Z | | | DP | | 0-0 | 77-21-11 | D41041P | 50 | | | GD01017 | ST.. | 2 | | 115-199 |
| 5001B | 24 | G2 | CF | | 4-6 | 34-13-21 | D40073P | 3 | | | TB0016Y | C019 | BJ | | ALL |
| 5001R | 24 | G2 | CF | | 0-0 | 34-13-21 | D40073P | 2 | | | TB0016Y | A019 | BJ | | ALL |
| 5001Z | | | CF | | 0-0 | 34-13-21 | D40073P | 1 | | | GD01242 | ST.. | 2 | | ALL |
| 5002B | 24 | G2 | CE | | 8-2 | 34-13-21 | D00285 | 31 | | | TB0016Y | C019 | BJ | | ALL |
| 5002R | 24 | G2 | CE | | 0-0 | 34-13-21 | D00285 | 30 | | | TB0016Y | A019 | BJ | | ALL |
| 5002Z | | | CE | | 0-0 | 34-13-21 | D00285 | DED | | | GD01242 | ST.. | 2 | | ALL |
| 5003B | 24 | G2 | CH | | 6-10 | 34-13-21 | D00287 | 31 | | | TB0016Y | C019 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 33

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5013B | 24 | G2 | CS | | 6-10 | 34-22-93 | D00801 | | 49 | | TB0016Y | C013 | BJ | | 115-199 |
| 5013R | 24 | G2 | CS | | 0-0 | 34-22-91 | D00185 | | 48 | | TB0016Y | A013 | BJ | | 001-099 |
| 5013R | 24 | G2 | CS | | 0-0 | 34-22-93 | D00801 | | 48 | | TB0016Y | A013 | BJ | | 115-199 |
| 5013Z | | | CS | | 0-0 | 34-22-91 | D00185 | DED | | | GD01242 | ST.. | 2 | | 001-099 |
| 5013Z | | | CS | | 0-0 | 34-22-93 | D00801 | DED | | | GD01242 | ST.. | 2 | | 115-199 |
| 5014B | 24 | G2 | CT | | 4-6 | 34-22-91 | D40073P | | 9 | | TB0016Y | C013 | BJ | | 001-099 |
| 5014B | 24 | G2 | CT | | 3-3 | 34-22-93 | D41041P | | 40 | | TB0016Y | C013 | BJ | | 115-199 |
| 5014R | 24 | G2 | CT | | 0-0 | 34-22-91 | D40073P | | 8 | | TB0016Y | A013 | BJ | | 001-099 |
| 5014R | 24 | G2 | CT | | 0-0 | 34-22-93 | D41041P | | 39 | | TB0016Y | A013 | BJ | | 115-199 |
| 5014Z | | | CT | | 0-0 | 34-22-91 | D40073P | | 10 | | GD01242 | ST.. | 2 | | 001-099 |
| 5014Z | | | CT | | 0-0 | 34-22-93 | D41041P | | 41 | | GD01242 | ST.. | 2 | | 115-199 |
| 5015B | 24 | G2 | CU | | 12-6 | 34-22-92 | D00189 | | 29 | | TB0014Y | C018 | BJ | | ALL |
| 5015R | 24 | G2 | CU | | 0-0 | 34-22-92 | D00189 | | 28 | | TB0014Y | A018 | BJ | | ALL |
| 5015Z | | | CU | | 0-0 | 34-22-92 | D00189 | DED | | | GD01013 | ST.. | 2 | | ALL |
| 5016B | 24 | G2 | AE | | 8-2 | 22-14-21 | D00285 | | 25 | | TB0016Y | A015 | BJ | | ALL |
| 5016R | 24 | G2 | AE | | 0-0 | 22-14-21 | D00285 | | 24 | | TB0016Y | C015 | BJ | | ALL |
| 5016Z | | | AE | | 0-0 | 22-14-21 | D00285 | DED | | | GD01241 | ST.. | 2 | | ALL |
| 5017B | 24 | G2 | AF | | 4-5 | 22-14-21 | D40099P | | 10 | | TB0016Y | A015 | BJ | | ALL |
| 5017R | 24 | G2 | AF | | 0-0 | 22-14-21 | D40099P | | 9 | | TB0016Y | C015 | BJ | | ALL |
| 5017Z | | | AF | | 0-0 | 22-14-21 | D40099P | | 11 | | GD01241 | ST.. | 2 | | ALL |
| 5027B | 24 | G2 | CW | | 8-10 | 34-22-91 | D00185 | | 42 | | D40035P | | 2 | | 001-099 |
| 5027B | 24 | G2 | CW | | 7-5 | 34-22-93 | D00801 | | 42 | | D40035P | | 2 | | 115-199 |
| 5027R | 24 | G2 | CW | | 0-0 | 34-22-91 | D00185 | | 41 | | D40035P | | 1 | | 001-099 |
| 5027R | 24 | G2 | CW | | 0-0 | 34-22-93 | D00801 | | 41 | | D40035P | | 1 | | 115-199 |
| 5027Z | | | CW | | 0-0 | 34-22-91 | D00185 | DED | | | D40035P | | | AA | 001-099 |
| 5027Z | | | CW | | 0-0 | 34-22-93 | D00801 | DED | | | D40035P | | | AA | 115-199 |
| 5028B | 24 | G2 | CV | | 7-8 | 34-22-92 | D00189 | | 31 | | D40073P | | 12 | | ALL |
| 5028R | 24 | G2 | CV | | 0-0 | 34-22-92 | D00189 | | 30 | | D40073P | | 11 | | ALL |
| 5028Z | | | CV | | 0-0 | 34-22-92 | D00189 | DED | | | D40073P | | | AB | ALL |
| 5030B | 24 | G2 | AH | | 7-8 | 31-25-11 | D00465 | | 23 | | D40099P | | 33 | | 001-099 |
| 5030B | 24 | G2 | AH | | 9-4 | 31-25-11 | D00465 | | 23 | | D40099P | | 33 | | 115-199 |
| 5030R | 24 | G2 | AH | | 0-0 | 31-25-11 | D00465 | | 24 | | D40099P | | 32 | | ALL |
| 5030Z | | | AH | | 0-0 | 31-25-11 | D00465 | DED | | | D40099P | | | AC | ALL |
| 5031B | 24 | G2 | DA | | 9-7 | 22-32-11 | D00397 | | 27 | | D40035P | | 43 | | ALL |
| 5031R | 24 | G2 | DA | | 0-0 | 22-32-11 | D00397 | | 26 | | D40035P | | 42 | | ALL |
| 5031Z | | | DA | | 0-0 | 22-32-11 | D00397 | DED | | | D40035P | | | AD | ALL |
| 5044B | 24 | G2 | DF | | 6-10 | 34-22-93 | D00801 | | 32 | | TB0016Y | C024 | BJ | | 115-199 |
| 5044R | 24 | G2 | DF | | 0-0 | 34-22-93 | D00801 | | 31 | | TB0016Y | A024 | BJ | | 115-199 |
| 5044Z | | | DF | | 0-0 | 34-22-93 | D00801 | DED | | | GD01242 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 35

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0003 | 286N0003 | | | FIRST OFFICER'S INST. PANELS(P3-1, P3-3); INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5045B | 24 | G2 | DG | | 3-3 | 34-22-93 | D41041P | | 37 | | TB0016Y | C024 | BJ | | 115-199 |
| 5045R | 24 | G2 | DG | | 0-0 | 34-22-93 | D41041P | | 36 | | TB0016Y | A024 | BJ | | 115-199 |
| 5045Z | | | DG | | 0-0 | 34-22-93 | D41041P | | 38 | | GD01242 | ST.. | 2 | | 115-199 |
| 5046B | 24 | G2 | DE | | 8-3 | 34-55-21 | D00813 | | 7 | | TB0015Y | A006 | BJ | | 115-199 |
| 5046R | 24 | G2 | DE | | 0-0 | 34-55-21 | D00813 | | 4 | | TB0015Y | C006 | BJ | | 115-199 |
| 5046Z | | | DE | | 0-0 | 34-55-21 | D00813 | DED | | | GD01248 | ST.. | 2 | | 115-199 |
| 5047B | 24 | G2 | DD | | 3-3 | 34-55-21 | D41041P | | 44 | | TB0015Y | A006 | BJ | | 115-199 |
| 5047R | 24 | G2 | DD | | 0-0 | 34-55-21 | D41041P | | 43 | | TB0015Y | C006 | BJ | | 115-199 |
| 5047Z | | | DD | | 0-0 | 34-55-21 | D41041P | | 45 | | GD01248 | ST.. | 2 | | 115-199 |
| 5048B | 24 | G2 | DH | | 10-5 | 34-55-11 | D00811 | | 7 | | TB0013Y | A013 | BJ | | 115-199 |
| 5048R | 24 | G2 | DH | | 0-0 | 34-55-11 | D00811 | | 4 | | TB0013Y | C013 | BJ | | 115-199 |
| 5048Z | | | DH | | 0-0 | 34-55-11 | D00811 | DED | | | GD01019 | ST.. | 2 | | 115-199 |
| 5050B | 24 | G2 | DV | | 8-3 | 34-22-91 | D00185 | | 32 | | TB0016Y | C025 | BJ | | 001-099 |
| 5050R | 24 | G2 | DV | | 0-0 | 34-22-91 | D00185 | | 31 | | TB0016Y | A025 | BJ | | 001-099 |
| 5050Z | | | DV | | 0-0 | 34-22-91 | D00185 | DED | | | GD01248 | ST.. | 2 | | 001-099 |
| 5051B | 24 | G2 | DK | | 3-3 | 34-22-91 | D41041P | | 37 | | TB0016Y | C025 | BJ | | 001-099 |
| 5051R | 24 | G2 | DK | | 0-0 | 34-22-91 | D41041P | | 36 | | TB0016Y | A025 | BJ | | 001-099 |
| 5051Z | | | DK | | 0-0 | 34-22-91 | D41041P | | 38 | | GD01248 | ST.. | 2 | | 001-099 |
| 5055B | 24 | G2 | DS | | 3-3 | 34-22-18 | D41041P | | 28 | | TB0016Y | C024 | BJ | | 115-199 |
| 5055R | 24 | G2 | DS | | 0-0 | 34-22-18 | D41041P | | 27 | | TB0016Y | A024 | BJ | | 115-199 |
| 5055Z | | | DS | | 0-0 | 34-22-18 | D41041P | | 29 | | GD01242 | ST.. | 2 | | 115-199 |
| FRAA | | | | | 0-0 | 34-22-91 | D40035P | | 3 | | D40035P | | | AA | 001-099 |
| FRAA | | | | | 0-0 | 34-22-93 | D40035P | | 3 | | D40035P | | | AA | 115-199 |
| FRAB | | | | | 0-0 | 34-22-92 | D40073P | | | AB | D40073P | 13 | | | ALL |
| FRAC | | | | | 0-0 | 31-25-11 | D40099P | | | AC | D40099P | 34 | | | ALL |
| FRAD | | | | | 0-0 | 22-32-11 | D40035P | | | AD | D40035P | 44 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0000

Page 36 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0010 | 286N0010 | | | P7 INTERNAL- CAPTAIN DIMMER CONTROLS | | | | | | | | | | | |
| 0001 | 22 | GA | | | 4-0 | 33-14-21 | R00503 | 1 | C | | D40850J | 21 | | | ALL |
| 0002 | 22 | GA | | | 4-0 | 33-14-21 | D40850J | 55 | | | L00279 | =G | C | | ALL |
| 0003 | 24 | GK | | | 4-0 | 33-14-11 | R00505 | 1 | C | | D40850J | 18 | | | ALL |
| 0004 | 22 | GA | | | 4-0 | 33-14-11 | R00505 | 2 | C | | D40850J | 19 | | | ALL |
| 0007 | 22 | GA | | | 4-0 | 33-11-11 | R00507 | A | \$ | | D40850J | 41 | | | ALL |
| 0008 | 22 | GA | | | 4-0 | 33-11-11 | R00507 | B | \$ | | D40850J | 42 | | | ALL |
| 0009 | 20 | GA | | | 2-0 | 33-11-11 | D00896 | 6 | | | D40850J | 10 | | | ALL |
| 0011 | 20 | GA | | | 4-0 | 33-13-41 | L00482 | =P | B | | D40850J | 1 | | | ALL |
| 0012 | 20 | GA | | | 4-0 | 33-13-41 | L00482 | =G | G | | D40850J | 2 | | | ALL |
| 0022 | 22 | GA | | | 2-0 | 33-16-51 | S00507 | 13 | 1A | | D40850J | 22 | | | ALL |
| 0023 | 22 | GA | | | 2-0 | 33-16-21 | S00507 | 18 | 1A | | D40850J | 23 | | | ALL |
| 0024 | 22 | GA | | | 2-0 | 33-16-51 | S00507 | 14 | 1A | | D40850J | 24 | | | ALL |
| 0025 | 22 | GA | | | 2-0 | 33-16-11 | S00507 | 17 | 1A | | D40850J | 25 | | | ALL |
| 0026 | 22 | GA | | | 2-0 | 31-51-21 | S00507 | 3 | 1A | | D40850J | 26 | | | ALL |
| 0027 | 22 | GA | | | 2-0 | 31-51-21 | S00507 | 15 | 1A | | D40850J | 27 | | | ALL |
| 0028 | 22 | GA | | | 2-0 | 31-51-21 | S00507 | 2 | 1A | | D40850J | 28 | | | ALL |
| 0029 | 22 | GA | | | 2-0 | 31-41-14 | S00507 | 16 | 1A | | D40850J | 29 | | | ALL |
| 0030 | 22 | GA | | | 2-0 | SPARE | S00507 | 5 | 1A | | D40850J | 45 | | | ALL |
| 0031 | 22 | GA | | | 2-0 | SPARE | S00507 | 6 | 1A | | D40850J | 46 | | | ALL |
| 0032 | 22 | GA | | | 2-0 | 31-41-14 | S00507 | 8 | 1A | | D40850J | 48 | | | ALL |
| 0033 | 22 | GA | | | 2-0 | 31-41-14 | S00507 | 9 | 1A | | D40850J | 49 | | | ALL |
| 2002B | 24 | GL | AB | | 2-0 | 33-11-11 | D00896 | 7 | | | D40850J | 44 | | | ALL |
| 2002R | 24 | GL | AB | | 0-0 | 33-11-11 | D00896 | 8 | | | D40850J | 43 | | | ALL |
| 2003B | 24 | GL | AC | | 2-0 | 33-11-11 | D00896 | 4 | | | D40850J | 4 | | | ALL |
| 2003R | 24 | GL | AC | | 0-0 | 33-11-11 | D00896 | 5 | | | D40850J | 5 | | | ALL |
| 2004B | 24 | GL | AD | | 2-0 | 33-11-11 | D00896 | 11 | | | D40850J | 6 | | | ALL |
| 2004R | 24 | GL | AD | | 0-0 | 33-11-11 | D00896 | 12 | | | D40850J | 7 | | | ALL |
| 2005B | 24 | PL | BC | | 3-4 | 23-51-11 | D40850J | 30 | | | S00441 | 1C | Z2 | | 115-199 |
| 2005R | 24 | PL | BC | | 0-0 | 23-51-11 | D40850J | 31 | | | S00441 | 1NO | Z2 | | 115-199 |
| 2501B | 22 | GF | AA | | 3-0 | 33-11-11 | R00507 | 3 | \$ | | D40850J | 9 | | | ALL |
| 2501R | 22 | GF | AA | | 0-0 | 33-11-11 | R00507 | 2 | \$ | | D40850J | 3 | | | ALL |
| 2501Z | | | AA | | 0-0 | 33-11-11 | R00507 | DED | | | D40850J | 8 | | | ALL |
| 3001B | 22 | GC | BA | | 4-0 | 33-13-11 | R00511 | 2 | \$ | | D40850J | 14 | | | ALL |
| 3001R | 22 | GC | BA | | 0-0 | 33-13-11 | R00511 | 3 | \$ | | D40850J | 13 | | | ALL |
| 3001Y | 22 | GC | BA | | 0-0 | 33-13-11 | R00511 | 1 | \$ | | D40850J | 15 | | | ALL |
| 3002B | 22 | GC | BB | | 4-0 | 31-25-11 | S00320 | 1C | Z2 | | D40850J | 38 | | | ALL |
| 3002R | 22 | GC | BB | | 0-0 | 31-25-11 | S00320 | 1NC | Z2 | | D40850J | 39 | | | ALL |
| 3002Y | 22 | GC | BB | | 0-0 | 31-25-11 | S00320 | 1NO | Z2 | | D40850J | 40 | | | ALL |
| A-BK | | | | | 0-0 | 34-22-15 | TS0187 | BLK | | | D40850J | 37 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0010

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0010 | 286N0010 | | | P7 INTERNAL- CAPTAIN DIMMER CONTROLS (continued) | | | | | | | | | | | |
| A-BL | | | | AE | 0-0 | 34-22-15 | TS0187 | BLU | | | D40850J | 34 | | | ALL |
| A-OR | | | | | 0-0 | 34-22-15 | TS0187 | ORG | | | D40850J | 35 | | | ALL |
| A-RD | | | | AE | 0-0 | 34-22-15 | TS0187 | RED | | | D40850J | 33 | | | ALL |
| A-YL | | | | | 0-0 | 34-22-15 | TS0187 | YEL | | | D40850J | 36 | | | ALL |
| B-BK | | | | | 0-0 | 33-11-21 | L00441 | W-B | | | D40850J | 17 | | | ALL |
| B-WT | | | | | 0-0 | 33-11-21 | L00441 | W-A | | | D40850J | 16 | | | ALL |
| C-WT | | | | | 0-0 | 33-14-21 | R00503 | 2 | C | | L00279 | WHT | | | ALL |
| W0012 | 286N0012 | | | P7 INTERNAL- FIRST OFFICER DIMMER CONTROLS | | | | | | | | | | | |
| 0001 | 22 | | GA | | 3-4 | 33-14-21 | R00504 | 1 | C | | D40854J | 21 | | | ALL |
| 0002 | 22 | | GA | | 3-2 | 33-14-21 | D40854J | 55 | | | L00280 | =G | C | | ALL |
| 0003 | 24 | | GK | | 3-3 | 33-14-11 | R00506 | 1 | C | | D40854J | 18 | | | ALL |
| 0004 | 22 | | GA | | 3-3 | 33-14-11 | R00506 | 2 | C | | D40854J | 19 | | | ALL |
| 0007 | 22 | | GA | | 3-3 | 33-11-11 | R00508 | A | \$ | | D40854J | 41 | | | ALL |
| 0008 | 22 | | GA | | 3-3 | 33-11-11 | R00508 | B | \$ | | D40854J | 42 | | | ALL |
| 0009 | 20 | | GA | | 2-0 | 33-11-11 | D00888 | 6 | | | D40854J | 10 | | | ALL |
| 0011 | 20 | | GA | | 3-4 | 33-13-41 | L00483 | =P | B | | D40854J | 1 | | | ALL |
| 0012 | 20 | | GA | | 3-5 | 33-13-41 | L00483 | =G | G | | D40854J | 2 | | | ALL |
| 0022 | 22 | | GA | | 2-1 | 33-16-61 | S00508 | 13 | 1A | | D40854J | 22 | | | ALL |
| 0023 | 22 | | GA | | 2-1 | 33-16-31 | S00508 | 18 | 1A | | D40854J | 23 | | | ALL |
| 0024 | 22 | | GA | | 2-1 | 33-16-51 | S00508 | 14 | 1A | | D40854J | 24 | | | ALL |
| 0025 | 22 | | GA | | 2-1 | 33-16-41 | S00508 | 17 | 1A | | D40854J | 25 | | | ALL |
| 0026 | 22 | | GA | | 2-1 | 31-51-21 | S00508 | 3 | 1A | | D40854J | 26 | | | ALL |
| 0027 | 22 | | GA | | 2-1 | 31-51-21 | S00508 | 15 | 1A | | D40854J | 27 | | | ALL |
| 0028 | 22 | | GA | | 2-1 | 31-51-21 | S00508 | 2 | 1A | | D40854J | 28 | | | ALL |
| 0029 | 22 | | GA | | 2-1 | 31-41-14 | S00508 | 16 | 1A | | D40854J | 29 | | | ALL |
| 0030 | 22 | | GA | | 2-1 | SPARE | S00508 | 5 | 1A | | D40854J | 45 | | | ALL |
| 0031 | 22 | | GA | | 2-1 | SPARE | S00508 | 6 | 1A | | D40854J | 46 | | | ALL |
| 0032 | 22 | | GA | | 2-1 | 31-41-14 | S00508 | 8 | 1A | | D40854J | 48 | | | ALL |
| 0033 | 22 | | GA | | 2-1 | 31-41-14 | S00508 | 9 | 1A | | D40854J | 49 | | | ALL |
| 2002B | 24 | | GL | AB | 2-0 | 33-11-11 | D00888 | 7 | | | D40854J | 44 | | | ALL |
| 2002R | 24 | | GL | AB | 0-0 | 33-11-11 | D00888 | 8 | | | D40854J | 43 | | | ALL |
| 2003B | 24 | | GL | AC | 2-0 | 33-11-11 | D00888 | 4 | | | D40854J | 4 | | | ALL |
| 2003R | 24 | | GL | AC | 0-0 | 33-11-11 | D00888 | 5 | | | D40854J | 5 | | | ALL |
| 2004B | 24 | | GL | AD | 2-0 | 33-11-11 | D00888 | 11 | | | D40854J | 6 | | | ALL |
| 2004R | 24 | | GL | AD | 0-0 | 33-11-11 | D00888 | 12 | | | D40854J | 7 | | | ALL |
| 2005B | 24 | | PL | BC | 3-4 | 23-51-21 | D40854J | 30 | | | S00442 | 1C | Z2 | | 115-199 |
| 2005R | 24 | | PL | BC | 0-0 | 23-51-21 | D40854J | 31 | | | S00442 | 1NO | Z2 | | 115-199 |
| 2501B | 22 | | GF | AA | 3-3 | 33-11-11 | R00508 | 3 | \$ | | D40854J | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0010

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|------------------------|------------------------|---------------|
| Wire No. | GA CO TY | Fam FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W0012 | 286N0012 | P7 INTERNAL- FIRST OFFICER DIMMER CONTROLS (continued) | | | |
| 2501R | 22 | GF AA | 0-0 33-11-11 R00508 | 2 \$ D40854J | 3 ALL |
| 2501Z | | AA | 0-0 33-11-11 R00508 | DED D40854J | 8 ALL |
| 3001B | 22 | GC BA | 3-4 33-13-21 R00512 | 2 \$ D40854J | 14 ALL |
| 3001R | 22 | GC BA | 0-0 33-13-21 R00512 | 3 \$ D40854J | 13 ALL |
| 3001Y | 22 | GC BA | 0-0 33-13-21 R00512 | 1 \$ D40854J | 15 ALL |
| 3002B | 22 | GC BB | 3-4 31-25-11 S00321 | 1C Z2 D40854J | 38 ALL |
| 3002R | 22 | GC BB | 0-0 31-25-11 S00321 | 1NC Z2 D40854J | 39 ALL |
| 3002Y | 22 | GC BB | 0-0 31-25-11 S00321 | 1NO Z2 D40854J | 40 ALL |
| A-BK | | | 0-0 34-22-25 TS0188 | BLK D40854J | 37 ALL |
| A-BL | | AF | 0-0 34-22-25 TS0188 | BLU D40854J | 34 ALL |
| A-OR | | | 0-0 34-22-25 TS0188 | ORG D40854J | 35 ALL |
| A-RD | | AF | 0-0 34-22-25 TS0188 | RED D40854J | 33 ALL |
| A-YL | | | 0-0 34-22-25 TS0188 | YEL D40854J | 36 ALL |
| B-BK | | | 0-0 33-11-21 L00442 | W-B D40854J | 17 ALL |
| B-WT | | | 0-0 33-11-21 L00442 | W-A D40854J | 16 ALL |
| C-WT | | | 0-0 33-14-21 R00504 | 2 C L00280 | WHT ALL |
| W0017 | 286N0017 | P1-1 CAPT INSTR PNL-L | | | |
| 0001 | 24 | GK | 2-0 34-22-82 D40671J | 4 S00004 | 2 1A ALL |
| 0002 | 20 | GA | 2-0 34-22-82 D40671J | 5 S00004 | 3 1A ALL |
| 0003 | 24 | GK | 2-0 34-22-17 D40671J | 11 S00004 | 6 1A ALL |
| 0004 | 20 | GA | 2-0 34-22-17 D40671J | 12 S00004 | 5 1A ALL |
| 0005 | 24 | GK | 2-4 34-22-17 D40671J | 13 S00001 | B 1A ALL |
| 0006 | 24 | GK | 2-4 34-22-17 D40671J | 14 S00001 | D 1A ALL |
| 0007 | 20 | GA | 2-4 34-22-17 D40671J | 15 S00001 | A 1A ALL |
| 0008 | 22 | GA | 2-0 34-22-17 D40671J | 16 S00003 | 5 1A ALL |
| 0009 | 20 | GA | 2-0 34-22-17 D40671J | 21 S00003 | 6 1A ALL |
| 0010 | 20 | GA | 2-1 34-22-17 D40671J | 10 S00002 | 2 1A 001-099 |
| 0010 | 20 | GA | 2-1 34-22-17 D40671J | 10 SM00001 | W 115-199 |
| 0011 | 24 | GK | 2-1 34-22-17 D40671J | 9 S00002 | 3 1A 001-099 |
| 0011 | 24 | GK | 2-1 34-22-17 D40671J | 9 S00002 | AA 1A 115-199 |
| 0012 | 24 | GK | 2-3 34-22-38 D40281J | 12 S00003 | 1 1A 001-099 |
| 0012 | 24 | GK | 2-3 34-22-37 D40281J | 12 S00003 | 1 1A 115-199 |
| 0013 | 24 | GK | 2-3 34-22-38 D40281J | 13 S00003 | 3 1A 001-099 |
| 0013 | 24 | GK | 2-3 34-22-37 D40281J | 13 S00003 | 3 1A 115-199 |
| 0014 | 24 | GK | 2-3 34-22-37 D40281J | 5 S00003 | 7 1A ALL |
| 0015 | 20 | GA | 2-3 34-22-37 D40281J | 6 S00003 | 9 1A ALL |
| 0016 | 24 | GK | 2-3 34-22-91 D40281J | 1 S00004 | 9 1A 001-099 |
| 0016 | 24 | GK | 2-3 34-22-93 D40281J | 1 S00004 | 9 1A 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0010

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0017 | 286N0017 | | | P1-1 CAPT INSTR PNL-L (continued) | | | | | | | | | | | |
| 0017 | 20 | | GA | | 2-3 | 34-22-91 | D40281J | | 14 | | S00004 | 8 | 1A | | 001-099 |
| 0017 | 20 | | GA | | 2-3 | 34-22-93 | D40281J | | 14 | | S00004 | 8 | 1A | | 115-199 |
| 0024 | 22 | | GA | | 2-1 | 34-12-61 | D40671J | | 35 | | S00482 | 7 | 1A | | ALL |
| 0025 | 22 | | GA | | 2-1 | 34-12-61 | D40671J | | 36 | | S00482 | 8 | 1A | | ALL |
| 0026 | 20 | | GA | | 1-6 | 33-13-11 | D40671J | | 22 | | SM00003 | | W | | ALL |
| 0027 | 20 | | GA | | 1-6 | 33-13-11 | D40671J | | 23 | | SM00004 | | W | | ALL |
| 0030 | 20 | | GA | | 2-1 | 34-12-61 | D40671J | | 24 | | S00482 | 6 | 1A | | ALL |
| 0031 | 22 | | GA | | 2-1 | 34-12-61 | D40671J | | 25 | | S00482 | 9 | 1A | | ALL |
| 0032 | 20 | | GA | | 2-1 | 34-12-61 | D40671J | | 26 | | S00482 | 3 | 1A | | ALL |
| 0033 | 20 | | GA | | 2-1 | 34-12-61 | D40671J | | 27 | | S00482 | 12 | 1A | | ALL |
| 0035 | 22 | | GA | | 2-1 | 34-12-61 | D40671J | | 29 | | S00482 | 11 | 1A | | ALL |
| 0036 | 22 | | GA | | 2-1 | 34-12-61 | D40671J | | 30 | | S00482 | 5 | 1A | | ALL |
| 0037 | 22 | | GA | | 2-1 | 34-13-11 | D40671J | | 31 | | S00482 | 2 | 1A | | ALL |
| 0039 | 22 | | GA | | 2-7 | 22-41-13 | D40281J | | 15 | | S00001 | G | 1A | | ALL |
| 0040 | 22 | | GA | | 2-7 | 22-41-13 | D40281J | | 16 | | S00001 | H | 1A | | ALL |
| 0041 | 22 | | GA | | 2-7 | 22-41-13 | D40281J | | 17 | | S00001 | J | 1A | | ALL |
| 0042 | 22 | | GA | | 2-7 | 22-41-13 | D40281J | | 18 | | S00001 | F | 1A | | ALL |
| 0043 | 22 | | GA | | 2-0 | 34-22-16 | D40671J | | 32 | | S00003 | 12 | 1A | | ALL |
| 0044 | 20 | | GA | | 2-0 | 34-22-16 | D40671J | | 33 | | S00003 | 11 | 1A | | ALL |
| 0046 | 20 | | GA | | 1-6 | 33-13-11 | SM00004 | | | W | L00361 | =G | G | | ALL |
| 0047 | 20 | | GA | | 1-5 | 33-13-11 | SM00003 | | | W | L00361 | =P | B | | ALL |
| 0048 | 20 | | GA | | 1-2 | 33-13-11 | SM00003 | | | W | S00482 | 13 | 1A | | ALL |
| 0049 | 20 | | GA | | 1-1 | 33-13-11 | SM00003 | | | W | S00002 | 13 | 1A | | 001-099 |
| 0050 | 20 | | GA | | 1-0 | 33-13-11 | SM00003 | | | W | S00003 | 13 | 1A | | ALL |
| 0051 | 20 | | GA | | 1-0 | 33-13-11 | SM00003 | | | W | S00004 | 13 | 1A | | ALL |
| 0052 | 20 | | GA | | 1-6 | 33-13-11 | SM00004 | | | W | GD01559 | AC.. | E | | ALL |
| 0053 | 20 | | GA | | 1-2 | 33-13-11 | SM00004 | | | W | S00482 | 15 | 1A | | ALL |
| 0054 | 20 | | GA | | 1-1 | 33-13-11 | SM00004 | | | W | S00002 | 15 | 1A | | 001-099 |
| 0055 | 20 | | GA | | 1-0 | 33-13-11 | SM00004 | | | W | S00003 | 15 | 1A | | ALL |
| 0056 | 20 | | GA | | 1-0 | 33-13-11 | SM00004 | | | W | S00004 | 15 | 1A | | ALL |
| 0057 | 22 | | GA | | 2-0 | 32-42-11 | D40671J | | 37 | | S00004 | 11 | 1A | | ALL |
| 0058 | 22 | | GA | | 2-0 | 32-42-11 | D40671J | | 38 | | S00004 | 12 | 1A | | ALL |
| 0059 | 24 | | GK | | 2-0 | 34-22-17 | D40671J | | 17 | | S00003 | 8 | 1A | | ALL |
| 0060 | 24 | | GK | | 2-1 | 34-61-15 | D40671J | | 6 | | S00002 | 11 | 1A | | 001-099 |
| 0060 | 24 | | GK | | 2-1 | 34-61-15 | D40671J | | 6 | | S00002 | AK | 1A | | 115-199 |
| 0061 | 24 | | GK | | 2-1 | 34-61-15 | D40671J | | 7 | | S00002 | 12 | 1A | | 001-099 |
| 0061 | 24 | | GK | | 2-1 | 34-61-15 | D40671J | | 7 | | S00002 | AH | 1A | | 115-199 |
| 0062 | 24 | | GK | | 2-4 | 34-61-25 | D40281J | | 3 | | S00002 | 5 | 1A | | 001-099 |
| 0063 | 24 | | GK | | 2-4 | 34-61-25 | D40281J | | 4 | | S00002 | 6 | 1A | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0010

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-----------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0017 | 286N0017 | | | | P1-1 CAPT INSTR PNL-L (continued) | | | | | | | | | | | |
| 0064 | 24 | | GK | | 2-3 | 34-22-38 | D40281J | 24 | | | | S00003 | 2 | 1A | | 001-099 |
| 0064 | 24 | | GK | | 2-3 | 34-22-37 | D40281J | 24 | | | | S00003 | 2 | 1A | | 115-199 |
| 0070 | 22 | | PA | | 2-1 | 34-61-16 | S00002 | AF | 1A | | | D40671J | 1 | | | 115-199 |
| 0071 | 22 | | PA | | 2-1 | 34-61-16 | S00002 | AE | 1A | | | D40671J | 2 | | | 115-199 |
| 0072 | 22 | | PA | | 2-1 | 34-61-16 | S00002 | BJ | 1A | | | D40671J | 3 | | | 115-199 |
| 0073 | 22 | | PA | | 2-1 | 34-61-16 | S00002 | BH | 1A | | | D40671J | 8 | | | 115-199 |
| 0075 | 22 | | PA | | 1-1 | 34-22-17 | S00002 | AB | 1A | | | SM00001 | | W | | 115-199 |
| 0076 | 22 | | PA | | 1-1 | 34-22-17 | S00002 | AD | 1A | | | SM00001 | | W | | 115-199 |
| 0077 | 22 | | PA | | 2-1 | 34-61-15 | S00002 | AJ | 1A | | | D40671J | 18 | | | 115-199 |
| 0100 | 22 | | PA | | 2-1 | 34-61-18 | S00002 | BF | 1A | | | D40671J | 28 | | | 115-199 |
| 0101 | 22 | | PA | | 2-1 | 34-61-18 | S00002 | BG | 1A | | | D40671J | 34 | | | 115-199 |
| 0102 | 22 | | PA | | 2-1 | 34-61-18 | S00002 | BE | 1A | | | D40671J | 39 | | | 115-199 |
| 0103 | 22 | | PA | | 2-1 | 34-61-18 | S00002 | BB | 1A | | | D40671J | 40 | | | 115-199 |
| 0104 | 22 | | PA | | 2-1 | 34-61-18 | S00002 | BC | 1A | | | D40671J | 19 | | | 115-199 |
| 0105 | 22 | | PA | | 2-1 | 34-61-18 | S00002 | BA | 1A | | | D40671J | 20 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0010

Page 5 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0033 | 286N0033 | | | P3-3 F/O INSTR PNL-R | | | | | | | | | | | |
| 0001 | 24 | | GK | | 2-1 | 34-22-92 | D40525J | 21 | | | S00012 | 2 | 1A | | ALL |
| 0002 | 20 | | GA | | 2-1 | 34-22-92 | D40525J | 22 | | | S00012 | 3 | 1A | | ALL |
| 0003 | 24 | | GK | | 2-1 | 34-22-27 | D40525J | 10 | | | S00012 | 6 | 1A | | ALL |
| 0004 | 20 | | GA | | 2-1 | 34-22-27 | D40525J | 11 | | | S00012 | 5 | 1A | | ALL |
| 0005 | 24 | | GK | | 2-4 | 34-22-27 | D40525J | 7 | | | S00009 | B | 1A | | ALL |
| 0006 | 24 | | GK | | 2-4 | 34-22-27 | D40525J | 8 | | | S00009 | D | 1A | | ALL |
| 0007 | 20 | | GA | | 2-4 | 34-22-27 | D40525J | 9 | | | S00009 | A | 1A | | ALL |
| 0008 | 20 | | GA | | 2-2 | 34-22-27 | D40525J | 17 | | | S00010 | 3 | 1A | | 001-099 |
| 0008 | 20 | | GA | | 2-2 | 34-22-27 | D40525J | 17 | | | S00010 | AA | 1A | | 115-199 |
| 0009 | 24 | | GK | | 2-2 | 34-22-27 | D40525J | 16 | | | S00010 | 1 | 1A | | 001-099 |
| 0009 | 24 | | GK | | 2-2 | 34-22-27 | D40525J | 16 | | | S00010 | AC | 1A | | 115-199 |
| 0010 | 20 | | GA | | 2-1 | 34-22-27 | D40525J | 28 | | | S00011 | 6 | 1A | | ALL |
| 0011 | 22 | | GA | | 2-1 | 34-22-27 | D40525J | 29 | | | S00011 | 5 | 1A | | ALL |
| 0012 | 24 | | GK | | 2-1 | 34-21-31 | D40525J | 27 | | | S00012 | 1 | 1A | | ALL |
| 0013 | 22 | | GA | | 2-10 | 34-32-11 | D40525J | 13 | | | L00242 | 2 | 1A | | ALL |
| 0014 | 22 | | GA | | 2-10 | 34-32-11 | D40525J | 14 | | | L00241 | 2 | 1A | | ALL |
| 0015 | 22 | | GA | | 2-10 | 34-32-11 | D40525J | 15 | | | L00240 | 2 | 1A | | ALL |
| 0016 | 20 | | GA | | 2-1 | 34-22-81 | D40525J | 2 | | | S00012 | 11 | 1A | | 001-099 |
| 0016 | 20 | | GA | | 2-1 | 34-22-83 | D40525J | 2 | | | S00012 | 11 | 1A | | 115-199 |
| 0017 | 24 | | GK | | 2-1 | 34-22-81 | D40525J | 1 | | | S00012 | 12 | 1A | | 001-099 |
| 0017 | 24 | | GK | | 2-1 | 34-22-83 | D40525J | 1 | | | S00012 | 12 | 1A | | 115-199 |
| 0018 | 24 | | GK | | 2-1 | 34-22-37 | D40525J | 18 | | | S00011 | 7 | 1A | | ALL |
| 0019 | 24 | | GK | | 2-1 | 34-22-37 | D40525J | 19 | | | S00011 | 9 | 1A | | ALL |
| 0021 | 20 | | GA | | 2-1 | 34-22-37 | D40525J | 25 | | | S00011 | 3 | 1A | | ALL |
| 0022 | 24 | | GK | | 2-1 | 34-22-37 | D40525J | 24 | | | S00011 | 2 | 1A | | ALL |
| 0023 | 22 | | GA | | 1-10 | 33-16-61 | SM00002 | | W | | L00240 | 1 | 1A | | ALL |
| 0024 | 22 | | GA | | 1-10 | 33-16-11 | L00240 | 3 | 1A | | SM00001 | | W | | 001-099 |
| 0024 | 22 | | GA | | 1-10 | 33-16-51 | L00240 | 3 | 1A | | SM00001 | | W | | 115-199 |
| 0025 | 22 | | GA | | 1-9 | 33-16-61 | L00241 | 1 | 1A | | SM00002 | | W | | ALL |
| 0026 | 22 | | GA | | 1-9 | 33-16-51 | L00241 | 3 | 1A | | SM00001 | | W | | ALL |
| 0027 | 22 | | GA | | 1-10 | 33-16-61 | L00242 | 1 | 1A | | SM00002 | | W | | ALL |
| 0028 | 22 | | GA | | 1-10 | 33-16-51 | L00242 | 3 | 1A | | SM00001 | | W | | ALL |
| 0029 | 22 | | GA | | 1-7 | 33-16-51 | D40525J | 5 | | | SM00001 | | W | | ALL |
| 0030 | 22 | | GA | | 1-7 | 33-16-61 | D40525J | 6 | | | SM00002 | | W | | ALL |
| 0031 | 20 | | GA | | 1-11 | 34-12-62 | S00483 | 9 | 1A | | D40249J | 5 | | | ALL |
| 0032 | 22 | | GA | | 2-1 | 34-12-62 | S00483 | 7 | 1A | | D40525J | 23 | | | ALL |
| 0033 | 24 | | GK | | 2-1 | 34-22-27 | D40525J | 31 | | | S00483 | 1 | 1A | | ALL |
| 0041 | 20 | | GA | | 1-5 | 33-13-21 | D40249J | 8 | | | SM00005 | | W | | ALL |
| 0042 | 20 | | GA | | 1-5 | 33-13-21 | D40249J | 9 | | | SM00006 | | W | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0030

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----------|-------|-------------|-------|----------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0033 | | 286N0033 | | | | P3-3 F/O INSTR PNL-R (continued) | | | | | | | | | |
| | 0043 | 22 | GA | | 2-1 | 34-12-62 | S00483 | 8 | 1A | | D40525J | 33 | | | ALL |
| | 0044 | 20 | GA | | 1-11 | 34-13-21 | S00483 | 2 | 1A | | D40249J | 10 | | | ALL |
| | 0045 | 20 | GA | | 1-11 | 34-12-62 | S00483 | 12 | 1A | | D40249J | 12 | | | ALL |
| | 0046 | 20 | GA | | 1-11 | 34-12-62 | S00483 | 3 | 1A | | D40249J | 11 | | | ALL |
| | 0047 | 20 | GA | | 1-11 | 34-12-62 | S00483 | 6 | 1A | | D40249J | 13 | | | ALL |
| | 0048 | 22 | GA | | 1-11 | 34-12-62 | S00483 | 11 | 1A | | D40249J | 14 | | | ALL |
| | 0049 | 22 | GA | | 1-11 | 34-12-62 | S00483 | 10 | 1A | | D40249J | 15 | | | ALL |
| | 0050 | 22 | GA | | 2-2 | 22-41-13 | D40249J | 16 | | | S00009 | G | 1A | | ALL |
| | 0051 | 22 | GA | | 2-2 | 22-41-13 | D40249J | 17 | | | S00009 | H | 1A | | ALL |
| | 0052 | 22 | GA | | 2-2 | 22-41-13 | D40249J | 18 | | | S00009 | J | 1A | | ALL |
| | 0053 | 20 | GA | | 2-2 | 22-41-13 | D40249J | 19 | | | S00009 | F | 1A | | ALL |
| | 0054 | 22 | GA | | 2-1 | 34-22-26 | D40525J | 34 | | | S00011 | 12 | 1A | | ALL |
| | 0055 | 20 | GA | | 2-1 | 34-22-26 | D40525J | 35 | | | S00011 | 11 | 1A | | ALL |
| | 0056 | 20 | GA | | 1-8 | 33-13-21 | SM00006 | | W | | L00367 | =G | G | | ALL |
| | 0057 | 20 | GA | | 1-7 | 33-13-21 | SM00005 | | W | | L00367 | =P | B | | ALL |
| | 0058 | 20 | GA | | 1-0 | 33-13-21 | SM00005 | | W | | S00483 | 13 | 1A | | ALL |
| I | 0059 | 20 | GA | | 1-2 | 33-13-21 | SM00005 | | W | | S00010 | 13 | 1A | | 001-099 |
| | 0060 | 20 | GA | | 1-0 | 33-13-21 | SM00005 | | W | | S00011 | 13 | 1A | | ALL |
| | 0061 | 20 | GA | | 1-0 | 33-13-21 | SM00005 | | W | | S00012 | 13 | 1A | | ALL |
| | 0062 | 20 | GA | | 1-6 | 33-13-21 | SM00006 | | W | | GD01561 | AC.. | E | | ALL |
| | 0063 | 20 | GA | | 1-0 | 33-13-21 | SM00006 | | W | | S00483 | 15 | 1A | | ALL |
| I | 0064 | 20 | GA | | 1-2 | 33-13-21 | SM00006 | | W | | S00010 | 15 | 1A | | 001-099 |
| | 0065 | 20 | GA | | 1-0 | 33-13-21 | SM00006 | | W | | S00011 | 15 | 1A | | ALL |
| | 0066 | 20 | GA | | 1-0 | 33-13-21 | SM00006 | | W | | S00012 | 15 | 1A | | ALL |
| | 0067 | 22 | GA | | 1-11 | 32-42-11 | D40249J | 21 | | | S00012 | 8 | 1A | | ALL |
| | 0068 | 22 | GA | | 1-11 | 32-42-11 | D40249J | 20 | | | S00012 | 9 | 1A | | ALL |
| | 0069 | 22 | GA | | 1-11 | 34-12-62 | D40249J | 22 | | | S00483 | 5 | 1A | | ALL |
| I | 0070 | 22 | PA | | 2-2 | 34-61-26 | D40525J | 4 | | | S00010 | AG | 1A | | 115-199 |
| I | 0071 | 22 | PA | | 2-2 | 34-61-26 | D40525J | 12 | | | S00010 | AE | 1A | | 115-199 |
| I | 0072 | 22 | PA | | 2-2 | 34-61-26 | D40525J | 20 | | | S00010 | BK | 1A | | 115-199 |
| I | 0080 | 22 | PA | | 2-2 | 34-61-25 | D40525J | 30 | | | S00010 | AK | 1A | | 115-199 |
| I | 0081 | 22 | PA | | 2-2 | 34-61-25 | D40525J | 32 | | | S00010 | AJ | 1A | | 115-199 |
| I | 0082 | 22 | PA | | 2-2 | 34-61-25 | D40525J | 26 | | | S00010 | AH | 1A | | 115-199 |
| I | 0100 | 22 | PA | | 2-2 | 34-61-18 | D40525J | 36 | | | S00010 | BC | 1A | | 115-199 |
| I | 0101 | 22 | PA | | 2-2 | 34-61-18 | D40525J | 37 | | | S00010 | BD | 1A | | 115-199 |
| I | 0102 | 22 | PA | | 2-2 | 34-61-18 | D40525J | 38 | | | S00010 | BA | 1A | | 115-199 |
| I | 0103 | 22 | PA | | 2-2 | 34-61-18 | D40525J | 39 | | | S00010 | BF | 1A | | 115-199 |
| I | 0104 | 22 | PA | | 2-2 | 34-61-18 | D40525J | 40 | | | S00010 | BG | 1A | | 115-199 |
| I | 0105 | 22 | PA | | 2-2 | 34-61-18 | D40525J | 41 | | | S00010 | BE | 1A | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0030

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|------------|--|-------------|----|----|----------------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0033 | | 286N0033 | | | P3-3 F/O INSTR PNL-R (continued) | | | | | | | | | | | |
| 0186 | | 24 | | GK | | 2-2 | 34-22-27 | D40525J | | 3 | | S00010 | 2 | 1A | | 001-099 |
| 0186 | | 24 | | GK | | 2-2 | 34-61-26 | D40525J | | 3 | | S00010 | BH | 1A | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0030

Page 3 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0041 | 286N0041 | | | P61 -ACCESSORY PANEL. | | | | | | | | | | | |
| 0001 | 22 | | GA | | 4-10 | 23-51-51 | D00455 | | 3 | | TB0121Z | 11 | BJ | | 115-199 |
| 0002 | 24 | | GK | | 0-7 | 23-51-51 | D00455 | | 23 | | D00455 | 24 | | | 115-199 |
| 0003 | 22 | | GA | | 4-10 | 23-51-51 | D00455 | | 4 | | GD00619 | DC.. | 2 | | 115-199 |
| 0005 | 20 | | GA | | 4-10 | 33-13-71 | D00455 | | 1 | | TB0121Z | 9 | BJ | | 115-199 |
| 0006 | 20 | | GA | | 4-10 | 33-13-71 | D00455 | | 2 | | GD00619 | AC.. | 2 | | 115-199 |
| 0013 | 20 | | GA | | 2-11 | 23-51-51 | D00455 | | | AA | GD02607 | ST.. | 2 | | 115-199 |
| 2001B | 24 | | GL | AA | 8-7 | 23-51-51 | D00455 | | 13 | | D00549 | 2 | | | 115-199 |
| 2001R | 24 | | GL | AA | 0-0 | 23-51-51 | D00455 | | 14 | | D00549 | 1 | | | 115-199 |
| 2501B | 24 | | G2 | AB | 8-7 | 23-51-51 | D00455 | | 15 | | D00549 | 4 | | | 115-199 |
| 2501R | 24 | | G2 | AB | 0-0 | 23-51-51 | D00455 | | 16 | | D00549 | 3 | | | 115-199 |
| 2501Z | | | | AB | 0-0 | 23-51-51 | D00455 | | | AA | D00549 | DED | | | 115-199 |
| 2502B | 24 | | G2 | AC | 2-11 | 23-51-51 | D00455 | | 8 | | D00555 | 2 | | | 115-199 |
| 2502R | 24 | | G2 | AC | 0-0 | 23-51-51 | D00455 | | 9 | | D00555 | 1 | | | 115-199 |
| 2502Z | | | | AC | 0-0 | 23-51-51 | D00455 | | | AA | D00555 | 3 | | | 115-199 |
| 3501B | 24 | | G3 | AD | 7-11 | 23-51-51 | D00455 | | 12 | | SP00325 | | 9 | | 115-199 |
| 3501R | 24 | | G3 | AD | 0-0 | 23-51-51 | D00455 | | 10 | | SP00327 | | 9 | | 115-199 |
| 3501Y | 24 | | G3 | AD | 0-0 | 23-51-51 | D00455 | | 11 | | SP00329 | | 9 | | 115-199 |
| 3501Z | | | | AD | 0-0 | 23-51-51 | D00455 | | | AA | SP00327 | DED | | | 115-199 |
| B-BK | | | | | 0-0 | 23-51-51 | D00551 | BLK | | | SP00329 | | 9 | | 115-199 |
| B-BL | | | | | 0-0 | 23-51-51 | D00551 | BLU | | | SP00325 | | 9 | | 115-199 |
| C-BK | | | | | 0-0 | 23-51-51 | D00553 | BLK | | | SP00329 | | 9 | | 115-199 |
| C-BL | | | | | 0-0 | 23-51-51 | D00553 | BLU | | | SP00325 | | 9 | | 115-199 |
| C-RD | | | | | 0-0 | 23-51-51 | D00553 | RED | | | SP00327 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0040

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0060 | 286N0060 | | | P6-1 MODULE WIRING- DC BUSES | | | | | | | | | | | |
| 0001 | 08 | | HA | | 4-6 | 24-33-11 | C00829 | =B | D | | K00104 | B2 | E | | ALL |
| 0002 | 12 | | HA | | 5-1 | 24-33-11 | C00872 | =L | D | | D01878 | A2 | | | ALL |
| 0003 | 12 | | HA | | 5-0 | 24-33-11 | C00811 | =B | D | * | D01878 | A3 | | | ALL |
| 0004 | 22 | | GA | | 5-1 | 24-33-11 | C00811 | =L | D | | D01678 | X1 | | | ALL |
| 0005 | 22 | | GA | | 4-0 | 24-34-11 | C04097 | =L | D | | TB0024Y | A008 | BJ | | ALL |
| 0006 | 22 | | GA | | 5-2 | 24-33-11 | C00828 | =L | D | | D01878 | X1 | | | ALL |
| 0007 | 22 | | GA | | 5-3 | 24-34-11 | C00879 | =L | D | | D40296J | 30 | | | ALL |
| 0010 | 12 | | HA | | 1-4 | 24-54-71 | C00804 | =B | D | | C04136 | =B | D | | ALL |
| 0012 | 08 | | HA | | 4-3 | 24-54-72 | C00827 | =B | D | * | TB5011 | 8 | E | | ALL |
| 0013 | 10 | | HA | | 1-3 | 24-54-72 | C00827 | =B | D | * | C01061 | =B | D | | 001-099 |
| 0013 | 10 | | HA | | 1-3 | 24-54-72 | C00827 | =B | D | * | C01061 | =B | D | * | 115-199 |
| 0014 | 22 | | GA | | 6-1 | 24-31-11 | C00827 | =L | D | | D01786 | X1 | | | ALL |
| 0015 | 22 | | GA | | 4-10 | 24-33-11 | C00814 | =L | D | | K00104 | X1 | C | | ALL |
| 0016 | 16 | | GA | | 6-3 | 34-21-11 | C00614 | =L | D | | D40246J | 1 | | | ALL |
| 0017 | 16 | | GA | | 4-8 | 34-21-31 | C00621 | =L | D | | TB5011 | 7 | E | | 001-099 |
| 0019 | 12 | | HA | | 1-4 | 24-54-72 | C01179 | =B | D | * | C04062 | =B | D | | 115-199 |
| 0020 | 10 | | HA | | 1-3 | 24-54-72 | C01179 | =B | D | * | C01061 | =B | D | * | 115-199 |
| 0021 | 22 | | GA | | 4-9 | 24-51-31 | C00880 | =L | D | | K00104 | 11 | C | | ALL |
| 0024 | 22 | | GA | | 6-4 | 29-21-31 | C04287 | =L | D | | D41904J | 13 | | | 001-099 |
| 0025 | 18 | | GA | | 6-2 | 28-21-11 | C01045 | =L | D | * | D40870J | 4 | 18 | | 001-099 |
| 0026 | 22 | | GA | | 5-5 | 24-25-11 | C04349 | =L | D | | D40870J | 23 | | | 001-002 |
| 0026 | 22 | | GA | | 5-5 | 24-25-11 | C04349 | =L | D | | D40870J | 14 | | | 003-099 |
| 0026 | 22 | | GA | | 5-5 | 24-25-11 | C04349 | CAP | Y | | D40870J | 23 | | | 115-199 |
| 0027 | 24 | | GK | | 6-2 | 21-58-12 | C04070 | =L | D | * | D40296J | 39 | | | ALL |
| 0031 | 20 | | GA | | 3-3 | 29-11-31 | TB0024X | D004 | BJ | | D40870J | 19 | | | 001-002, 115-199 |
| 0031 | 20 | | GA | | 3-3 | 29-11-31 | TB0024X | D004 | BJ | | D40870J | 9 | | | 003-099 |
| 0036 | 16 | | GA | | 4-8 | 34-21-31 | C00621 | =L | D | | TB5011 | 7 | E | | 115-199 |
| 0101 | 22 | | GA | | 6-0 | 76-11-12 | C04137 | =L | D | | D40870J | 21 | | | 001-002, 115-199 |
| 0101 | 22 | | GA | | 6-0 | 76-11-12 | C04137 | =L | D | | D40870J | 2 | | | 003-099 |
| 0103 | 22 | | GA | | 6-2 | 28-25-21 | C01063 | =L | D | | D40296J | 36 | | | ALL |
| 0105 | 20 | | GA | | 6-4 | 26-21-11 | C00787 | =L | D | * | D40296J | 10 | | | ALL |
| 0106 | 20 | | GA | | 6-5 | 26-21-11 | C00779 | =L | D | * | D41904J | 3 | | | ALL |
| 0109 | 16 | | GA | | 6-2 | 28-21-11 | C01043 | =L | D | | D40870J | 11 | 16 | | ALL |
| 0111 | 16 | | GA | | 6-2 | 28-21-11 | C01045 | =L | D | * | D40870J | 13 | 16 | | 001-099 |
| 0111 | 16 | | GA | | 6-2 | 28-21-11 | C01045 | =L | D | | D40870J | 13 | 16 | | 115-199 |
| 0115 | 22 | | GA | | 6-3 | 21-58-11 | C04070 | =L | D | * | D40870J | 15 | | | ALL |
| 0116 | 16 | | GA | | 6-3 | 28-21-11 | C01046 | =L | D | | D40870J | 16 | 16 | | 001-002, 115-199 |
| 0116 | 16 | | GA | | 6-3 | 28-21-11 | C01046 | =L | D | | D40870J | 12 | 16 | | 003-099 |
| 0120 | 20 | | GA | | 6-4 | 28-22-21 | C01062 | =L | D | | D40870J | 20 | | | 001-002, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0060 | | 286N0060 | | | | P6-1 MODULE WIRING- DC BUSSES (continued) | | | | | | | | | |
| 0120 | 20 | GA | | | 6-4 | 28-22-21 | C01062 | =L | D | | D40870J | 3 | | | 003-099 |
| 0121 | 20 | GA | | | 6-5 | 26-23-11 | C00773 | =L | D | | D40296J | 16 | | | ALL |
| 0201 | 20 | GA | | | 6-0 | 24-11-11 | C00804 | =L | D | | D40246J | 5 | | | ALL |
| 0202 | 20 | GA | | | 5-5 | 24-11-21 | C00805 | =L | D | | D40246J | 9 | | | ALL |
| 0203 | 20 | GA | | | 5-5 | 24-22-41 | C00806 | =L | D | | D40246J | 7 | | | ALL |
| 0204 | 20 | GA | | | 5-5 | 24-41-11 | C00809 | =L | D | | D40246J | 14 | | | ALL |
| 0205 | 22 | GA | | | 6-0 | 76-11-11 | C04136 | =L | D | | D41904J | 1 | | | ALL |
| 0206 | 18 | GA | | | 6-6 | 32-35-11 | C04177 | =L | D | | D40246J | 22 | 18 | | ALL |
| 0207 | 20 | GA | | | 6-4 | 28-22-21 | C01061 | =L | D | | D41904J | 8 | | | ALL |
| 0208 | 22 | GA | | | 6-6 | 24-34-11 | C04217 | =L | D | * | D40246J | 20 | | | ALL |
| 0209 | 16 | GA | | | 5-5 | 34-21-21 | C00620 | =L | D | | D00145 | B2 | | | ALL |
| 0211 | 20 | GA | | | 6-5 | 26-21-11 | C00778 | =L | D | * | D40296J | 9 | | | ALL |
| 0212 | 20 | GA | | | 6-5 | 26-21-11 | C00786 | =L | D | * | D41904J | 2 | | | ALL |
| 0213 | 20 | GA | | | 6-4 | 26-22-21 | C00780 | =L | D | * | D40296J | 37 | | | 001-099 |
| 0213 | 20 | GA | | | 6-5 | 26-22-21 | C00780 | =L | D | | D40870J | 5 | | | 115-199 |
| 0214 | 20 | GA | | | 6-5 | 26-22-21 | C00780 | =L | D | * | D41904J | 15 | | | 001-099 |
| 0301 | 16 | GA | | | 5-4 | 24-11-11 | C00807 | =L | D | | D40296J | 21 | | | ALL |
| 0302 | 22 | GA | | | 6-5 | 32-44-11 | C01179 | =L | D | | D40870J | 17 | | | 001-002, 115-199 |
| 0302 | 22 | GA | | | 6-5 | 32-44-11 | C01179 | =L | D | | D40870J | 10 | | | 003-099 |
| 0303 | 16 | GA | | | 5-4 | 24-11-21 | C00808 | =L | D | | D40296J | 23 | | | ALL |
| 0304 | 22 | GA | | | 6-4 | 31-25-11 | C00563 | =L | D | | D40296J | 24 | | | ALL |
| 0305 | 22 | GA | | | 6-3 | 31-25-11 | C00576 | =L | D | | D40296J | 22 | | | ALL |
| 0306 | 22 | GA | | | 6-4 | 24-33-11 | C04217 | =L | D | * | D40296J | 1 | | | ALL |
| 0307 | 20 | GA | | | 6-5 | 26-23-11 | C00781 | =L | D | | D41904J | 7 | | | ALL |
| 0310 | 10 | HA | | | 4-9 | 32-35-11 | C04248 | =L | D | | TB5011 | 9 | E | | ALL |
| 0311 | 06 | CQ | | | 4-7 | 24-31-11 | C04248 | =B | D | | TB5010 | =1 | F | | ALL |
| 0312 | 18 | GA | | | 4-11 | 29-21-31 | C04062 | =L | D | | TB5011 | 10 | E | | ALL |
| 0401 | 12 | HA | | | 7-1 | 24-54-73 | C00811 | =B | D | * | D40244J | 1 | | | ALL |
| 0403 | 20 | GA | | | 6-5 | 26-21-11 | C00778 | =L | D | * | D40296J | 14 | | | ALL |
| 0404 | 20 | GA | | | 6-4 | 26-21-11 | C00786 | =L | D | * | D40296J | 15 | | | ALL |
| 0405 | 20 | GA | | | 6-5 | 26-21-11 | C00787 | =L | D | * | D41904J | 5 | | | ALL |
| 0406 | 20 | GA | | | 6-5 | 26-21-11 | C00779 | =L | D | * | D41904J | 6 | | | ALL |
| ZZAA | 03 | ZB | | | 0-0 | 24-54-71 | C00879 | =B | D | | C04097 | =B | D | | ALL |
| ZZAB | 00 | ZB | | | 0-0 | 24-54-71 | C04097 | =B | D | | C00828 | =B | D | | ALL |
| ZZAC | 00 | ZB | | | 0-0 | 24-54-71 | C00828 | =B | D | | C00879 | =B | D | | ALL |
| ZZBB | 02 | ZB | | | 0-0 | 24-33-11 | C00872 | =B | D | | C00829 | =B | D | | ALL |
| ZZCC | 06 | ZB | | | 0-0 | 24-54-71 | C00808 | =B | D | | C00804 | =B | D | | ALL |
| ZZCD | 00 | ZB | | | 0-0 | 24-54-71 | C00804 | =B | D | | C00805 | =B | D | | ALL |
| ZZCE | 00 | ZB | | | 0-0 | 24-54-71 | C00805 | =B | D | | C00806 | =B | D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0060 | 286N0060 | | | P6-1 MODULE WIRING- DC BUSES (continued) | | | | | | | | | | | |
| ZZCF | 00 | | ZB | | 0-0 | 24-54-71 | C00806 | =B | D | | C00809 | =B | D | | ALL |
| ZZCG | 00 | | ZB | | 0-0 | 24-54-71 | C00809 | =B | D | | C00807 | =B | D | | ALL |
| ZZCH | 00 | | ZB | | 0-0 | 24-54-71 | C00807 | =B | D | | C00808 | =B | D | | ALL |
| ZZEE | 02 | | ZB | | 0-0 | 24-54-71 | C04137 | =B | D | | C04136 | =B | D | | ALL |
| ZZFF | 06 | | ZB | | 0-0 | 24-54-72 | C00827 | =B | D | | C04070 | =B | D | | ALL |
| ZZFG | 00 | | ZB | | 0-0 | 24-54-72 | C04070 | =B | D | | C00620 | =B | D | | ALL |
| ZZFH | 00 | | ZB | | 0-0 | 24-54-72 | C00814 | =B | D | | C00614 | =B | D | | ALL |
| ZZFI | 00 | | ZB | | 0-0 | 24-54-72 | C00614 | =B | D | | C00621 | =B | D | | ALL |
| ZZFJ | 00 | | ZB | | 0-0 | 24-54-72 | C00621 | =B | D | | C00620 | =B | D | | ALL |
| ZZFK | 00 | | ZB | | 0-0 | 24-54-72 | C00814 | =B | D | | C00827 | =B | D | | ALL |
| ZZGD | 02 | | ZB | | 0-0 | 24-54-72 | C04287 | =B | D | | C04062 | =B | D | | 001-099 |
| ZZGG | 02 | | ZB | | 0-0 | 24-54-72 | C04177 | =B | D | | C01179 | =B | D | | ALL |
| ZZGH | 00 | | ZB | | 0-0 | 24-54-72 | C01061 | =B | D | | C01062 | =B | D | | ALL |
| ZZGI | 00 | | ZB | | 0-0 | 24-54-72 | C01062 | =B | D | | C01063 | =B | D | | ALL |
| ZZGJ | 00 | | ZB | | 0-0 | 24-54-72 | C01063 | =B | D | | C01045 | =B | D | | ALL |
| ZZHH | 06 | | ZB | | 0-0 | 24-54-72 | C01046 | =B | D | | C01061 | =B | D | | ALL |
| ZZHI | 00 | | ZB | | 0-0 | 24-54-72 | C01045 | =B | D | | C01043 | =B | D | | ALL |
| ZZHJ | 00 | | ZB | | 0-0 | 24-54-72 | C01046 | =B | D | | C01043 | =B | D | | ALL |
| ZZHK | 02 | | ZB | | 0-0 | 24-54-72 | C04217 | =B | D | | C00880 | =B | D | | 001-099 |
| ZZHK | 00 | | ZB | | 0-0 | 24-54-72 | C04217 | =B | D | | C00880 | =B | D | | 115-199 |
| ZZJJ | 03 | | ZB | | 0-0 | 24-54-72 | C00576 | =B | D | | C00780 | =B | D | | 001-099 |
| ZZJJ | 06 | | ZB | | 0-0 | 24-54-72 | C00880 | =B | D | | C00780 | =B | D | | 115-199 |
| ZZJK | 00 | | ZB | | 0-0 | 24-54-72 | C00780 | =B | D | | C00563 | =B | D | | ALL |
| ZZJL | 00 | | ZB | | 0-0 | 24-54-72 | C00563 | =B | D | | C00576 | =B | D | | ALL |
| ZZJM | 00 | | ZB | | 0-0 | 24-54-72 | C00576 | =B | D | | C04217 | =B | D | | 115-199 |
| ZZKK | 06 | | ZB | | 0-0 | 24-54-72 | C00778 | =B | D | | C00773 | =B | D | | ALL |
| ZZKL | 00 | | ZB | | 0-0 | 24-54-72 | C00787 | =B | D | | C00779 | =B | D | | ALL |
| ZZKM | 00 | | ZB | | 0-0 | 24-54-72 | C00786 | =B | D | | C00779 | =B | D | | ALL |
| ZZKN | 00 | | ZB | | 0-0 | 24-54-72 | C00786 | =B | D | | C00778 | =B | D | | ALL |
| ZZKP | 00 | | ZB | | 0-0 | 24-54-72 | C00787 | =B | D | | C00781 | =B | D | | ALL |
| ZZKQ | 00 | | ZB | | 0-0 | 24-54-72 | C00773 | =B | D | | C00781 | =B | D | | ALL |
| ZZXA | 02 | | ZA | | 0-3 | 24-54-71 | C04097 | =B | D | | C00808 | =B | D | | ALL |
| ZZXB | 02 | | ZA | | 0-0 | 24-54-71 | C04137 | =B | D | | C04349 | =B | D | | ALL |
| ZZXD | 02 | | ZA | | 0-3 | 24-54-72 | C00780 | =B | D | | C00778 | =B | D | | ALL |
| ZZXE | 02 | | ZA | | 0-3 | 24-54-71 | C00829 | =L | D | | C00804 | =B | D | | ALL |
| ZZXG | 02 | | ZA | | 0-3 | 24-54-72 | C04177 | =B | D | | C00880 | =B | D | | ALL |
| ZZXH | 02 | | ZA | | 0-0 | 24-54-72 | C04062 | =B | D | | C01061 | =B | D | | 001-099 |
| ZZXJ | 02 | | ZA | | 0-0 | 24-54-72 | C00576 | =B | D | | C04217 | =B | D | | 001-099 |
| ZZXK | 02 | | ZA | | 0-0 | 24-54-72 | C01179 | =B | D | | C04287 | =B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286N0062 | | | P6-3 MODULE WIRING - LEFT AC BUSES | | | | | | | | | | | |
| 0001 | 06 | | CQ | | 6-0 | 24-51-11 | C00310 | A1 | D | * | TB5012 | 1 | F | | 001-099 |
| 0001 | 06 | | CQ | | 4-9 | 24-51-11 | C00310 | A1 | D | * | TB5012 | 1 | F | | 115-199 |
| 0002 | 06 | | CQ | | 6-0 | 24-51-11 | C00310 | B1 | D | * | TB5012 | 2 | F | | 001-099 |
| 0002 | 06 | | CQ | | 4-9 | 24-51-11 | C00310 | B1 | D | * | TB5012 | 2 | F | | 115-199 |
| 0003 | 06 | | CQ | | 6-0 | 24-51-11 | C00310 | C1 | D | * | TB5012 | 3 | F | | 001-099 |
| 0003 | 06 | | CQ | | 4-11 | 24-51-11 | C00310 | C1 | D | * | TB5012 | 3 | F | | 115-199 |
| 0004 | 10 | | HA | | 2-0 | 24-51-11 | C00312 | A2 | D | | C00313 | A2 | D | * | ALL |
| 0005 | 10 | | HA | | 2-0 | 24-51-11 | C00312 | B2 | D | | C00313 | B2 | D | * | ALL |
| 0006 | 10 | | HA | | 2-0 | 24-51-11 | C00312 | C2 | D | | C00313 | C2 | D | * | ALL |
| 0007 | 12 | | HA | | 2-0 | 24-51-11 | C00313 | A2 | D | * | C00369 | A1 | D | * | ALL |
| 0008 | 12 | | HA | | 2-0 | 24-51-11 | C00313 | B2 | D | * | C00369 | B1 | D | * | ALL |
| 0009 | 12 | | HA | | 2-0 | 24-51-11 | C00313 | C2 | D | * | C00369 | C1 | D | * | ALL |
| 0010 | 12 | | HA | | 2-0 | 24-51-13 | C00368 | A2 | D | | C00366 | A1 | D | * | ALL |
| 0011 | 12 | | HA | | 2-0 | 24-51-13 | C00368 | B2 | D | | C00366 | B1 | D | * | ALL |
| 0012 | 12 | | HA | | 2-0 | 24-51-13 | C00368 | C2 | D | | C00366 | C1 | D | * | ALL |
| 0013 | 10 | | HA | | 7-0 | 24-51-13 | C00310 | A2 | D | | TB5013 | 1 | E | | 001-099 |
| 0013 | 12 | | HA | | 7-0 | 24-51-13 | C00310 | A2 | D | | TB5013 | 1 | E | | 115-199 |
| 0014 | 10 | | HA | | 7-0 | 24-51-13 | C00310 | B2 | D | | TB5013 | 2 | E | | 001-099 |
| 0014 | 12 | | HA | | 7-0 | 24-51-13 | C00310 | B2 | D | | TB5013 | 2 | E | | 115-199 |
| 0015 | 10 | | HA | | 7-0 | 24-51-13 | C00310 | C2 | D | | TB5013 | 3 | E | | 001-099 |
| 0015 | 12 | | HA | | 7-0 | 24-51-13 | C00310 | C2 | D | | TB5013 | 3 | E | | 115-199 |
| 0016 | 14 | | GA | | 3-0 | 24-51-11 | C00308 | C1 | D | | C00877 | =B | D | * | ALL |
| 0017 | 14 | | GA | | 3-0 | 24-51-11 | C00308 | B1 | D | | C00876 | =B | D | * | ALL |
| 0019 | 12 | | HA | | 7-0 | 24-51-13 | C00366 | A1 | D | * | TB5013 | 1 | E | | ALL |
| 0020 | 12 | | HA | | 7-0 | 24-51-13 | C00366 | B1 | D | * | TB5013 | 2 | E | | ALL |
| 0021 | 12 | | HA | | 7-0 | 24-51-13 | C00366 | C1 | D | * | TB5013 | 3 | E | | ALL |
| 0025 | 18 | | GA | | 7-0 | 24-33-11 | C00874 | =L | D | * | D01680 | 4 | | | ALL |
| 0026 | 18 | | GA | | 7-0 | 24-33-11 | C00874 | =L | D | * | D01680 | 1 | 18 | | ALL |
| 0027 | 22 | | GA | | 10-0 | 24-51-31 | C00876 | =L | D | | D00544 | B3 | | | ALL |
| 0029 | 12 | | HA | | 2-0 | 24-51-13 | C00331 | A1 | D | | C01112 | =B | D | | ALL |
| 0035 | 14 | | GA | | 2-0 | 24-51-11 | C00876 | =B | D | * | C04329 | =B | D | | ALL |
| 0036 | 14 | | GA | | 2-0 | 24-51-11 | C00877 | =B | D | * | C04330 | =B | D | | ALL |
| 0037 | 20 | | GA | | 7-0 | 29-11-31 | C04329 | =L | D | | D40866J | 23 | | | 001-099 |
| 0037 | 20 | | GA | | 6-0 | 29-11-31 | C04329 | =L | D | | D40866J | 23 | | | 115-199 |
| 0038 | 20 | | GA | | 7-0 | 29-11-22 | C04330 | =L | D | | D40866J | 32 | | | 001-099 |
| 0038 | 20 | | GA | | 6-0 | 29-11-22 | C04330 | =L | D | | D40866J | 20 | | | 115-199 |
| 0043 | 16 | | GA | | 6-0 | 24-51-72 | C04266 | =L | D | | D04118P | 17 | | | ALL |
| 0044 | 16 | | GA | | 6-0 | 24-51-72 | C04265 | =L | D | | D04118P | 16 | | | ALL |
| 0045 | 16 | | GA | | 6-0 | 24-51-72 | C04264 | =L | D | | D04118P | 6 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | 286N0062 | | | P6-3 MODULE WIRING - LEFT AC BUSSES (continued) | | | | | | | | | | | |
| 0046 | 20 | GA | | | 3-0 | 24-51-72 | D04118P | 7 | | | GD00529 | AC.. | 2 | | ALL |
| 0047 | 16 | GA | | | 4-0 | 24-51-72 | D04118P | 4 | | | TB5019 | 8 | E | | ALL |
| 0048 | 16 | GA | | | 4-0 | 24-51-72 | D04118P | 12 | | | TB5019 | 9 | E | | ALL |
| 0049 | 16 | GA | | | 4-0 | 24-51-72 | D04118P | 13 | | | TB5019 | 10 | E | | ALL |
| 0050 | 20 | GA | | | 3-0 | 24-51-72 | D04118P | 15 | | | GD00529 | AC.. | 2 | | ALL |
| 0051 | 20 | GA | | | 3-0 | 24-51-72 | D04118P | 18 | | | GD00529 | ST.. | 2 | | ALL |
| 0052 | 20 | GA | | | 3-0 | 24-51-72 | D04118P | 19 | | | GD00529 | DC.. | 2 | | ALL |
| 0053 | 16 | GA | | | 10-0 | 24-51-12 | C04266 | =B | D | | C00308 | C2 | D | * | ALL |
| 0054 | 16 | GA | | | 10-0 | 24-51-12 | C04265 | =B | D | | C00308 | B2 | D | * | ALL |
| 0055 | 16 | GA | | | 10-0 | 24-51-12 | C04264 | =B | D | | C00308 | A2 | D | * | ALL |
| 0056 | 08 | HA | | | 0-11 | 24-51-11 | C00310 | A1 | D | * | C00313 | A2 | D | | ALL |
| 0057 | 08 | HA | | | 2-0 | 24-51-11 | C00310 | B1 | D | * | C00313 | B2 | D | | ALL |
| 0058 | 08 | HA | | | 1-0 | 24-51-11 | C00310 | C1 | D | * | C00313 | C2 | D | | ALL |
| 0068 | 12 | HA | | | 2-0 | 24-51-11 | C00369 | A1 | D | * | C00326 | A1 | D | | ALL |
| 0069 | 12 | HA | | | 2-0 | 24-51-11 | C00369 | B1 | D | * | C00326 | B1 | D | | ALL |
| 0070 | 12 | HA | | | 2-0 | 24-51-11 | C00369 | C1 | D | * | C00326 | C1 | D | | ALL |
| 0101 | 14 | GA | | | 3-0 | 24-53-11 | D40866J | 1 | | | D40240J | 4 | | | ALL |
| 0102 | 16 | GA | | | 7-0 | 28-22-11 | C00369 | C2 | D | | D40866J | 2 | | | ALL |
| 0103 | 20 | GA | | | 6-0 | 24-53-11 | C00877 | =L | D | | D40866J | 3 | | | ALL |
| 0104 | 16 | GA | | | 7-0 | 28-22-11 | C00369 | A2 | D | | D40866J | 4 | | | ALL |
| 0105 | 24 | GK | | | 6-0 | 30-31-11 | C01110 | =L | D | | D40866J | 5 | | | 001-099 |
| 0105 | 20 | GA | | | 6-0 | 30-31-11 | C01110 | =L | D | | D40866J | 5 | | | 115-199 |
| 0106 | 16 | GA | | | 7-0 | 28-22-11 | C00369 | B2 | D | | D40866J | 6 | | | ALL |
| 0107 | 24 | GK | | | 6-0 | 30-31-11 | C01112 | =L | D | | D40866J | 7 | | | 001-099 |
| 0107 | 20 | GA | | | 6-0 | 30-31-11 | C01112 | =L | D | | D40866J | 7 | | | 115-199 |
| 0112 | 18 | GA | | | 7-0 | 28-22-11 | C00366 | C2 | D | | D40866J | 12 | 18 | | ALL |
| 0113 | 18 | GA | | | 7-0 | 28-22-11 | C00366 | A2 | D | | D40866J | 13 | 18 | | ALL |
| 0114 | 18 | GA | | | 7-0 | 28-22-11 | C00366 | B2 | D | | D40866J | 14 | 18 | | ALL |
| 0115 | 18 | GA | | | 7-0 | 28-22-11 | C00368 | C1 | D | | D40866J | 15 | 18 | | ALL |
| 0116 | 18 | GA | | | 7-0 | 28-22-11 | C00368 | A1 | D | | D40866J | 16 | 18 | | ALL |
| 0117 | 18 | GA | | | 7-0 | 28-22-11 | C00368 | B1 | D | | D40866J | 17 | 18 | | ALL |
| 0121 | 22 | GA | | | 7-0 | 30-32-11 | C01134 | =L | D | | D40866J | 21 | | | ALL |
| 0201 | 16 | GA | | | 8-0 | 24-51-12 | C00308 | A2 | D | * | D40240J | 1 | | | ALL |
| 0202 | 16 | GA | | | 8-0 | 24-51-12 | C00308 | B2 | D | * | D40240J | 2 | | | ALL |
| 0203 | 16 | GA | | | 8-0 | 24-51-12 | C00308 | C2 | D | * | D40240J | 3 | | | ALL |
| 0205 | 16 | GA | | | 7-0 | 24-51-11 | C00313 | C1 | D | | D40240J | 5 | | | ALL |
| 0206 | 16 | GA | | | 7-0 | 24-51-11 | C00313 | B1 | D | | D40240J | 6 | | | ALL |
| 0207 | 16 | GA | | | 7-0 | 24-51-11 | C00313 | A1 | D | | D40240J | 7 | | | ALL |
| 0303 | 14 | GA | | | 7-0 | 24-32-11 | C00312 | A1 | D | | D40242J | 3 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0062 | | 286N0062 | | | | P6-3 MODULE WIRING - LEFT AC BUSSES (continued) | | | | | | | | | |
| | 0304 | 14 | GA | | 7-0 | 24-32-11 | C00312 | B1 | D | | D40242J | 4 | | | ALL |
| | 0305 | 14 | GA | | 7-0 | 24-32-11 | C00312 | C1 | D | | D40242J | 5 | | | ALL |
| | 0306 | 16 | GA | | 7-0 | 21-58-13 | C00331 | A2 | D | | D40242J | 6 | | | ALL |
| | 0307 | 16 | GA | | 7-0 | 21-58-13 | C00331 | B2 | D | | D40242J | 7 | | | ALL |
| | 0308 | 16 | GA | | 7-0 | 21-58-13 | C00331 | C2 | D | | D40242J | 8 | | | ALL |
| | 0309 | 22 | GA | | 8-0 | 21-58-15 | C03044 | A2 | D | | D40866J | 24 | | | 001-099 |
| I | 0309 | 22 | GA | | 7-0 | 21-58-15 | C03044 | CAP | Y | | D40866J | 24 | | | 115-199 |
| | 0310 | 22 | GA | | 8-0 | 21-58-15 | C03044 | B2 | D | | D40866J | 28 | | | 001-099 |
| I | 0310 | 22 | GA | | 7-0 | 21-58-15 | C03044 | CAP | Y | | D40866J | 28 | | | 115-199 |
| | 0311 | 22 | GA | | 8-0 | 21-58-15 | C03044 | C2 | D | | D40866J | 30 | | | 001-099 |
| I | 0311 | 22 | GA | | 7-0 | 21-58-15 | C03044 | CAP | Y | | D40866J | 30 | | | 115-199 |
| | 0370 | 12 | HA | | 7-0 | 24-51-15 | C03044 | A1 | D | * | TB5019 | 4 | E | | 001-099 |
| | 0370 | 12 | HA | | 6-1 | 24-51-15 | TB5019 | 4 | E | | C03044 | A1 | D | * | 115-199 |
| | 0371 | 12 | HA | | 7-0 | 24-51-15 | C03044 | B1 | D | * | TB5019 | 5 | E | | 001-099 |
| | 0371 | 12 | HA | | 6-1 | 24-51-15 | TB5019 | 5 | E | | C03044 | B1 | D | * | 115-199 |
| | 0372 | 12 | HA | | 7-0 | 24-51-15 | C03044 | C1 | D | * | TB5019 | 6 | E | | 001-099 |
| | 0372 | 12 | HA | | 6-1 | 24-51-15 | TB5019 | 6 | E | | C03044 | C1 | D | * | 115-199 |
| | 0373 | 12 | HA | | 3-0 | 24-51-15 | C03044 | C1 | D | * | C04353 | =B | D | | 001-099 |
| | 0373 | 12 | HA | | 2-7 | 24-51-15 | C03044 | C1 | D | * | C04353 | =B | D | | 115-199 |
| | 0374 | 14 | GA | | 7-0 | 24-51-15 | C00326 | A2 | D | | TB5019 | 1 | E | | 001-099 |
| | 0374 | 14 | GA | | 6-0 | 24-51-15 | C00326 | A2 | D | | TB5019 | 1 | E | | 115-199 |
| | 0375 | 14 | GA | | 7-0 | 24-51-15 | C00326 | B2 | D | | TB5019 | 2 | E | | 001-099 |
| | 0375 | 14 | GA | | 6-0 | 24-51-15 | C00326 | B2 | D | | TB5019 | 2 | E | | 115-199 |
| | 0376 | 14 | GA | | 7-0 | 24-51-15 | C00326 | C2 | D | | TB5019 | 3 | E | | 001-099 |
| | 0376 | 14 | GA | | 6-0 | 24-51-15 | C00326 | C2 | D | | TB5019 | 3 | E | | 115-199 |
| | 0377 | 22 | GA | | 6-0 | 24-51-15 | C04353 | =L | D | | T10040 | HV2 | E | | 001-099 |
| | 0377 | 22 | GA | | 5-0 | 24-51-15 | C04353 | =L | D | | T10040 | HV2 | E | | 115-199 |
| | 0378 | 16 | GA | | 3-0 | 24-51-15 | T10040 | GD | E | | GD00529 | AC.. | 2 | | ALL |
| | 0386 | 12 | HA | | 2-0 | 24-51-15 | C01110 | =B | D | * | C00874 | =B | D | | 001-099 |
| | 0386 | 12 | HA | | 1-8 | 24-51-15 | C01110 | =B | D | * | C00874 | =B | D | | 115-199 |
| | 0387 | 18 | GA | | 2-0 | 24-51-15 | T10040 | LV | E | | TB5019 | 7 | E | | ALL |
| | 0388 | 12 | HA | | 3-0 | 24-51-15 | C03044 | A1 | D | * | C01110 | =B | D | * | 001-099 |
| | 0388 | 12 | HA | | 2-7 | 24-51-15 | C03044 | A1 | D | * | C01110 | =B | D | * | 115-199 |
| | 0389 | 12 | HA | | 3-0 | 24-51-15 | C03044 | B1 | D | * | C01134 | =B | D | | 001-099 |
| | 0389 | 12 | HA | | 2-5 | 24-51-15 | C03044 | B1 | D | * | C01134 | =B | D | | 115-199 |
| | ZZXD | 02 | ZA | | 0-3 | 24-51-11 | C00308 | A1 | D | | C00312 | A2 | D | | ALL |
| | ZZXE | 02 | ZA | | 0-3 | 24-51-11 | C00308 | B1 | D | | C00312 | B2 | D | | ALL |
| | ZZXF | 02 | ZA | | 0-3 | 24-51-11 | C00308 | C1 | D | | C00312 | C2 | D | | ALL |
| | ZZXG | 02 | ZA | | 0-3 | 24-51-13 | C00331 | A1 | D | | C00368 | A2 | D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|--------|------|--------|-------|------|---------|--------|------|-------------|---------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W0062 | 286N0062 | | | | P6-3 MODULE WIRING - LEFT AC BUSSES (continued) | | | | | | | | | | | | | |
| ZZXH | 02 | | ZA | | 0-3 | 24-51-13 | | C00331 | | B1 | D | | C00368 | | B2 | D | ALL | |
| ZZXJ | 02 | | ZA | | 0-3 | 24-51-13 | | C00331 | | C1 | D | | C00368 | | C2 | D | ALL | |
| W0064 | 286N0064 | | | | P6-4 MODULE WIRING - RIGHT AC BUSSES | | | | | | | | | | | | | |
| 0001 | 06 | | CQ | | 5-5 | 24-51-21 | | C00317 | | A1 | D | * | TB5014 | | 1 | F | 001-099 | |
| 0001 | 06 | | CQ | | 5-0 | 24-51-21 | | C00317 | | A1 | D | * | TB5014 | | 1 | F | 115-199 | |
| 0002 | 06 | | CQ | | 5-7 | 24-51-21 | | C00317 | | B1 | D | * | TB5014 | | 2 | F | 001-099 | |
| 0002 | 06 | | CQ | | 5-3 | 24-51-21 | | C00317 | | B1 | D | * | TB5014 | | 2 | F | 115-199 | |
| 0003 | 06 | | CQ | | 5-9 | 24-51-21 | | C00317 | | C1 | D | * | TB5014 | | 3 | F | 001-099 | |
| 0003 | 06 | | CQ | | 5-4 | 24-51-21 | | C00317 | | C1 | D | * | TB5014 | | 3 | F | 115-199 | |
| 0004 | 10 | | HA | | 1-3 | 24-51-21 | | C00318 | | A2 | D | | C00319 | | A2 | D | * | ALL |
| 0005 | 10 | | HA | | 1-3 | 24-51-21 | | C00318 | | B2 | D | | C00319 | | B2 | D | * | ALL |
| 0006 | 10 | | HA | | 1-2 | 24-51-21 | | C00318 | | C2 | D | | C00319 | | C2 | D | * | ALL |
| 0007 | 08 | | HA | | 6-5 | 24-51-23 | | C00317 | | A2 | D | | TB5016 | | 1 | E | | 001-099 |
| 0007 | 08 | | HA | | 6-0 | 24-51-23 | | C00317 | | A2 | D | | TB5016 | | 1 | E | | 115-199 |
| 0008 | 08 | | HA | | 6-5 | 24-51-23 | | C00317 | | B2 | D | | TB5016 | | 2 | E | | 001-099 |
| 0008 | 08 | | HA | | 6-0 | 24-51-23 | | C00317 | | B2 | D | | TB5016 | | 2 | E | | 115-199 |
| 0009 | 08 | | HA | | 6-3 | 24-51-23 | | C00317 | | C2 | D | | TB5016 | | 3 | E | | 001-099 |
| 0009 | 08 | | HA | | 6-0 | 24-51-23 | | C00317 | | C2 | D | | TB5016 | | 3 | E | | 115-199 |
| 0010 | 08 | | HA | | 6-1 | 24-51-23 | | C03014 | | A1 | D | * | TB5016 | | 1 | E | | 001-099 |
| 0010 | 08 | | HA | | 6-0 | 24-51-23 | | C03014 | | A1 | D | * | TB5016 | | 1 | E | | 115-199 |
| 0011 | 08 | | HA | | 6-1 | 24-51-23 | | C03014 | | B1 | D | * | TB5016 | | 2 | E | | 001-099 |
| 0011 | 08 | | HA | | 5-11 | 24-51-23 | | C03014 | | B1 | D | * | TB5016 | | 2 | E | | 115-199 |
| 0012 | 08 | | HA | | 6-1 | 24-51-23 | | C03014 | | C1 | D | * | TB5016 | | 3 | E | | 001-099 |
| 0012 | 08 | | HA | | 5-10 | 24-51-23 | | C03014 | | C1 | D | * | TB5016 | | 3 | E | | 115-199 |
| 0013 | 12 | | HA | | 1-5 | 24-51-23 | | C00323 | | A1 | D | * | C03014 | | A1 | D | * | 001-099 |
| 0013 | 12 | | HA | | 1-3 | 24-51-23 | | C00323 | | A1 | D | * | C03014 | | A1 | D | * | 115-199 |
| 0014 | 12 | | HA | | 1-5 | 24-51-23 | | C00323 | | B1 | D | * | C03014 | | B1 | D | * | 001-099 |
| 0014 | 12 | | HA | | 1-2 | 24-51-23 | | C00323 | | B1 | D | * | C03014 | | B1 | D | * | 115-199 |
| 0015 | 12 | | HA | | 1-5 | 24-51-23 | | C00323 | | C1 | D | * | C03014 | | C1 | D | * | 001-099 |
| 0015 | 12 | | HA | | 1-3 | 24-51-23 | | C00323 | | C1 | D | * | C03014 | | C1 | D | * | 115-199 |
| 0016 | 12 | | HA | | 1-9 | 24-51-23 | | C00323 | | A1 | D | * | C00371 | | A2 | D | | 001-099 |
| 0016 | 12 | | HA | | 1-6 | 24-51-23 | | C00323 | | A1 | D | * | C00371 | | A2 | D | | 115-199 |
| 0017 | 12 | | HA | | 1-9 | 24-51-23 | | C00323 | | B1 | D | * | C00371 | | B2 | D | | 001-099 |
| 0017 | 12 | | HA | | 1-6 | 24-51-23 | | C00323 | | B1 | D | * | C00371 | | B2 | D | | 115-199 |
| 0018 | 12 | | HA | | 1-9 | 24-51-23 | | C00323 | | C1 | D | * | C00371 | | C2 | D | | 001-099 |
| 0018 | 12 | | HA | | 1-6 | 24-51-23 | | C00323 | | C1 | D | * | C00371 | | C2 | D | | 115-199 |
| 0020 | 14 | | GA | | 2-0 | 24-51-21 | | C00327 | | B1 | D | * | C04331 | | = B | D | | ALL |
| 0021 | 20 | | GA | | 8-11 | 29-11-31 | | C04331 | | = L | D | | TB0024X | | D004 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|--|-------|-------------|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0064 | 286N0064 | P6-4 MODULE WIRING - RIGHT AC BUSSES (continued) | | | | | | | | | | | | | |
| 0021 | 20 | GA | | | 9-0 | 29-11-31 | C04331 | =L | D | | TB0024X | D004 | BJ | | 115-199 |
| 0022 | 14 | GA | | | 2-0 | 24-51-21 | C00307 | A1 | D | | C00370 | A2 | D | * | 001-002, 115-199 |
| 0022 | 12 | HA | | | 2-4 | 24-51-21 | C00307 | A1 | D | | C00327 | A1 | D | | 003-099 |
| 0023 | 14 | GA | | | 2-0 | 24-51-21 | C00307 | B1 | D | | C00370 | B2 | D | * | 001-002 |
| 0023 | 12 | HA | | | 2-4 | 24-51-21 | C00307 | B1 | D | | C00327 | B1 | D | * | 003-099 |
| 0023 | 14 | GA | | | 2-0 | 24-51-21 | C00307 | B1 | D | | C00370 | B2 | D | | 115-199 |
| 0024 | 14 | GA | | | 2-0 | 24-51-21 | C00307 | C1 | D | * | C00370 | C2 | D | * | 001-002, 115-199 |
| 0024 | 12 | HA | | | 2-4 | 24-51-21 | C00307 | C1 | D | * | C00327 | C1 | D | | 003-099 |
| 0025 | 12 | HA | | | 2-2 | 24-51-23 | C00332 | A2 | D | | C01135 | =B | D | | 001-099 |
| 0025 | 12 | HA | | | 2-1 | 24-51-23 | C00332 | A2 | D | | C01135 | =B | D | | 115-199 |
| 0026 | 12 | HA | | | 1-5 | 24-51-52 | C03007 | A2 | D | * | C00397 | A2 | D | * | 001-099 |
| 0026 | 12 | HA | | | 1-6 | 24-51-52 | C03007 | A2 | D | * | C00397 | A2 | D | * | 115-199 |
| 0027 | 12 | HA | | | 2-1 | 24-51-23 | C00332 | B2 | D | | C01116 | =B | D | | 001-099 |
| 0027 | 12 | HA | | | 2-0 | 24-51-23 | C00332 | B2 | D | | C01116 | =B | D | | 115-199 |
| 0028 | 12 | HA | | | 1-5 | 24-51-52 | C03007 | B2 | D | * | C00397 | B2 | D | * | ALL |
| 0029 | 12 | HA | | | 1-5 | 24-51-52 | C03007 | C2 | D | * | C00397 | C2 | D | * | ALL |
| 0030 | 12 | HA | | | 1-6 | 24-51-52 | C00397 | A2 | D | * | C00372 | A1 | D | * | 001-099 |
| 0030 | 12 | HA | | | 1-6 | 24-51-52 | C00372 | A1 | D | * | C00397 | A2 | D | * | 115-199 |
| 0031 | 12 | HA | | | 1-7 | 24-51-52 | C00397 | B2 | D | * | C00372 | B1 | D | * | 001-099 |
| 0031 | 12 | HA | | | 1-7 | 24-51-52 | C00372 | B1 | D | * | C00397 | B2 | D | * | 115-199 |
| 0032 | 12 | HA | | | 1-7 | 24-51-52 | C00397 | C2 | D | * | C00372 | C1 | D | * | 001-099 |
| 0032 | 12 | HA | | | 1-7 | 24-51-52 | C00372 | C1 | D | * | C00397 | C2 | D | * | 115-199 |
| 0033 | 12 | HA | | | 2-7 | 24-51-21 | C00878 | =B | D | | C00307 | C1 | D | * | ALL |
| 0034 | 12 | HA | | | 6-6 | 24-51-52 | C03007 | A2 | D | * | TB5015 | 1 | E | | 001-099 |
| 0034 | 12 | HA | | | 5-11 | 24-51-52 | C03007 | A2 | D | * | TB5015 | 1 | E | | 115-199 |
| 0035 | 12 | HA | | | 6-6 | 24-51-52 | C03007 | B2 | D | * | TB5015 | 2 | E | | 001-099 |
| 0035 | 12 | HA | | | 6-0 | 24-51-52 | C03007 | B2 | D | * | TB5015 | 2 | E | | 115-199 |
| 0036 | 12 | HA | | | 6-6 | 24-51-52 | C03007 | C2 | D | * | TB5015 | 3 | E | | 001-099 |
| 0036 | 12 | HA | | | 6-0 | 24-51-52 | C03007 | C2 | D | * | TB5015 | 3 | E | | 115-199 |
| 0040 | 12 | HA | | | 2-1 | 24-51-52 | C00372 | A1 | D | * | C03020 | A2 | D | | ALL |
| 0041 | 12 | HA | | | 2-1 | 24-51-52 | C00372 | B1 | D | * | C03020 | B2 | D | | ALL |
| 0042 | 12 | HA | | | 2-1 | 24-51-52 | C00372 | C1 | D | * | C03020 | C2 | D | | ALL |
| 0043 | 18 | GA | | | 8-10 | 25-29-11 | C03020 | C1 | D | | D00880 | =P | D | | 001-099 |
| 0043 | 18 | GA | | | 8-0 | 25-29-11 | C03020 | C1 | D | | D00880 | =P | D | | 115-199 |
| 0044 | 18 | GA | | | 3-2 | 25-29-11 | D00880 | =G | D | | GD00529 | ST.. | 2 | | 001-099 |
| 0044 | 18 | GA | | | 4-0 | 25-29-11 | D00880 | =G | D | | GD00529 | ST.. | 2 | | 115-199 |
| 0045 | 18 | GA | | | 3-2 | 25-29-11 | D00880 | =N | D | | GD00529 | AC.. | 2 | | 001-099 |
| 0045 | 18 | GA | | | 4-0 | 25-29-11 | D00880 | =N | D | | GD00529 | AC.. | 2 | | 115-199 |
| 0055 | 22 | GA | | | 2-11 | 24-51-72 | TB5016 | 4 | E | | D04118P | 9 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|-------|---------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0064 | 286N0064 | | | P6-4 MODULE WIRING - RIGHT AC BUSSES (continued) | | | | | | | | | | | |
| 0055 | 22 | GA | | | 3-0 | 24-51-72 | TB5016 | | 4 | E | | D04118P | 9 | | 115-199 |
| 0056 | 22 | GA | | | 2-11 | 24-51-72 | TB5016 | | 5 | E | | D04118P | 8 | | 001-099 |
| 0056 | 22 | GA | | | 3-0 | 24-51-72 | TB5016 | | 5 | E | | D04118P | 8 | | 115-199 |
| 0057 | 22 | GA | | | 2-11 | 24-51-72 | TB5016 | | 6 | E | | D04118P | 2 | | 001-099 |
| 0057 | 22 | GA | | | 3-0 | 24-51-72 | TB5016 | | 6 | E | | D04118P | 2 | | 115-199 |
| 0058 | 08 | HA | | | 1-2 | 24-51-21 | C00317 | | A1 | D | * | C00319 | A2 | D | 001-099 |
| 0058 | 08 | HA | | | 0-8 | 24-51-21 | C00317 | | A1 | D | * | C00319 | A2 | D | 115-199 |
| 0059 | 08 | HA | | | 1-2 | 24-51-21 | C00317 | | B1 | D | * | C00319 | B2 | D | ALL |
| 0060 | 08 | HA | | | 1-2 | 24-51-21 | C00317 | | C1 | D | * | C00319 | C2 | D | ALL |
| 0064 | 14 | GA | | | 2-4 | 24-51-21 | C00370 | | A2 | D | * | C00327 | A1 | D | 001-002 |
| 0064 | 14 | HA | | | 2-0 | 24-51-21 | C00370 | | A2 | D | * | C00327 | A1 | D | 115-199 |
| 0065 | 14 | GA | | | 2-0 | 24-51-21 | C00370 | | B2 | D | * | C00327 | B1 | D | 001-002 |
| 0065 | 14 | HA | | | 2-0 | 24-51-21 | C00370 | | B2 | D | | C00327 | B1 | D | 115-199 |
| 0066 | 14 | GA | | | 2-4 | 24-51-21 | C00370 | | C2 | D | * | C00327 | C1 | D | 001-002 |
| 0066 | 14 | HA | | | 2-0 | 24-51-21 | C00370 | | C2 | D | * | C00327 | C1 | D | 115-199 |
| 0081 | 18 | GA | | | 8-0 | 24-51-25 | C00327 | | A2 | D | | TB5025 | 1 | E | 001-002 |
| 0081 | 12 | HA | | | 8-0 | 24-51-25 | C00327 | | A2 | D | | TB5025 | 1 | E | 003-099 |
| 0081 | 18 | GA | | | 7-0 | 24-51-25 | C00327 | | A2 | D | | TB5025 | 1 | E | 115-199 |
| 0082 | 18 | GA | | | 8-0 | 24-51-25 | C00327 | | B2 | D | | TB5025 | 2 | E | 001-002 |
| 0082 | 12 | HA | | | 8-0 | 24-51-25 | C00327 | | B2 | D | | TB5025 | 2 | E | 003-099 |
| 0082 | 18 | GA | | | 7-0 | 24-51-25 | C00327 | | B2 | D | | TB5025 | 2 | E | 115-199 |
| 0083 | 18 | GA | | | 8-0 | 24-51-25 | C00327 | | C2 | D | | TB5025 | 3 | E | 001-002 |
| 0083 | 12 | HA | | | 8-0 | 24-51-25 | C00327 | | C2 | D | | TB5025 | 3 | E | 003-099 |
| 0083 | 18 | GA | | | 7-0 | 24-51-25 | C00327 | | C2 | D | | TB5025 | 3 | E | 115-199 |
| 0084 | 12 | HA | | | 5-4 | 24-51-25 | TB5025 | | 4 | E | | C04355 | =B | D | 001-002 |
| 0084 | 12 | HA | | | 5-4 | 24-51-25 | TB5025 | | 4 | E | * | C04355 | =B | D | 003-099 |
| 0084 | 12 | HA | | | 5-1 | 24-51-25 | TB5025 | | 4 | E | | C04355 | =B | D | 115-199 |
| 0085 | 16 | GA | | | 2-2 | 24-51-25 | T10041 | | GD | E | | GD00529 | AC.. | 2 | 001-099 |
| 0085 | 16 | GA | | | 3-0 | 24-51-25 | T10041 | | GD | E | | GD00529 | AC.. | 2 | 115-199 |
| 0086 | 12 | HA | | | 5-4 | 24-51-25 | C01114 | | =B | D | | TB5025 | 5 | E | 001-002 |
| 0086 | 12 | HA | | | 5-4 | 24-51-25 | C01114 | | =B | D | | TB5025 | 5 | E | 003-099 |
| 0086 | 12 | HA | | | 5-5 | 24-51-25 | C01114 | | =B | D | | TB5025 | 5 | E | 115-199 |
| 0087 | 18 | GA | | | 2-6 | 24-51-25 | T10041 | | LV | E | | D40868J | 43 | | 001-099 |
| 0087 | 18 | GA | | | 3-0 | 24-51-25 | T10041 | | LV | E | | D40868J | 43 | | 115-199 |
| 0088 | 22 | GA | | | 5-4 | 24-51-25 | C04355 | | =L | D | | T10041 | HV2 | E | 001-099 |
| 0088 | 22 | GA | | | 6-0 | 24-51-25 | C04355 | | CAP | Y | | T10041 | HV2 | E | 115-199 |
| 0102 | 16 | GA | | | 7-2 | 28-22-11 | C00370 | | C1 | D | | D40868J | 31 | | 001-099 |
| 0102 | 16 | GA | | | 8-0 | 28-22-11 | C00370 | | C1 | D | | D40868J | 31 | | 115-199 |
| 0104 | 16 | GA | | | 7-2 | 28-22-11 | C00370 | | A1 | D | | D40868J | 32 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0064 | 286N0064 | | | P6-4 MODULE WIRING - RIGHT AC BUSSES (continued) | | | | | | | | | | | |
| 0104 | 16 | | GA | | 8-0 | 28-22-11 | C00370 | A1 | D | | D40868J | 32 | | | 115-199 |
| 0105 | 24 | | GK | | 6-2 | 30-31-12 | C01116 | =L | D | | D40868J | 5 | | | 001-099 |
| 0105 | 24 | | GK | | 7-0 | 30-31-12 | C01116 | =L | D | | D40868J | 5 | | | 115-199 |
| 0106 | 16 | | GA | | 7-2 | 28-22-11 | C00370 | B1 | D | | D40868J | 33 | | | 001-099 |
| 0106 | 16 | | GA | | 8-0 | 28-22-11 | C00370 | B1 | D | | D40868J | 33 | | | 115-199 |
| 0111 | 24 | | GK | | 6-2 | 30-31-12 | C01114 | =L | D | | D40868J | 11 | | | 001-099 |
| 0111 | 24 | | GK | | 7-0 | 30-31-12 | C01114 | =L | D | | D40868J | 11 | | | 115-199 |
| 0112 | 18 | | GA | | 6-11 | 28-22-11 | C00372 | C2 | D | | D40868J | 39 | | | 001-099 |
| 0112 | 18 | | GA | | 8-0 | 28-22-11 | C00372 | C2 | D | | D40868J | 39 | | | 115-199 |
| 0113 | 18 | | GA | | 6-11 | 28-22-11 | C00372 | A2 | D | | D40868J | 37 | | | 001-099 |
| 0113 | 18 | | GA | | 7-0 | 28-22-11 | C00372 | A2 | D | | D40868J | 37 | | | 115-199 |
| 0114 | 18 | | GA | | 6-11 | 28-22-11 | C00372 | B2 | D | | D40868J | 38 | | | 001-099 |
| 0114 | 18 | | GA | | 8-0 | 28-22-11 | C00372 | B2 | D | | D40868J | 38 | | | 115-199 |
| 0115 | 18 | | GA | | 6-11 | 28-22-11 | C00371 | C1 | D | | D40868J | 36 | | | 001-099 |
| 0115 | 18 | | GA | | 7-0 | 28-22-11 | C00371 | C1 | D | | D40868J | 36 | | | 115-199 |
| 0116 | 18 | | GA | | 6-11 | 28-22-11 | C00371 | A1 | D | | D40868J | 34 | | | 001-099 |
| 0116 | 18 | | GA | | 7-0 | 28-22-11 | C00371 | A1 | D | | D40868J | 34 | | | 115-199 |
| 0117 | 18 | | GA | | 6-11 | 28-22-11 | C00371 | B1 | D | | D40868J | 35 | | | 001-099 |
| 0117 | 18 | | GA | | 7-0 | 28-22-11 | C00371 | B1 | D | | D40868J | 35 | | | 115-199 |
| 0118 | 12 | | HA | | 6-11 | 24-51-25 | C00370 | A2 | D | | TB5025 | 6 | E | | 003-099 |
| 0119 | 12 | | HA | | 6-11 | 24-51-25 | C00370 | B2 | D | | TB5025 | 5 | E | * | 003-099 |
| 0120 | 12 | | HA | | 6-11 | 24-51-25 | C00370 | C2 | D | | TB5025 | 4 | E | * | 003-099 |
| 0121 | 22 | | GA | | 6-3 | 30-32-11 | C01135 | =L | D | | D40868J | 21 | | | 001-099 |
| 0121 | 22 | | GA | | 7-0 | 30-32-11 | C01135 | =L | D | | D40868J | 21 | | | 115-199 |
| 0128 | 18 | | GA | | 7-0 | 38-15-11 | C00397 | A1 | D | | D40868J | 28 | | | ALL |
| 0129 | 18 | | GA | | 7-0 | 38-15-11 | C00397 | B1 | D | | D40868J | 29 | | | ALL |
| 0130 | 18 | | GA | | 7-0 | 38-15-11 | C00397 | C1 | D | | D40868J | 30 | | | ALL |
| 0201 | 20 | | GA | | 6-4 | 30-33-11 | C04003 | =L | D | | D40250J | 1 | | | 001-099 |
| 0201 | 20 | | GA | | 7-0 | 30-33-11 | C04003 | =L | D | | D40250J | 1 | | | 115-199 |
| 0202 | 20 | | GA | | 7-0 | 24-53-21 | C00878 | =L | D | | D40250J | 2 | | | ALL |
| 0203 | 14 | | GA | | 7-2 | 27-81-11 | C03014 | A2 | D | | D40250J | 3 | | | 001-099 |
| 0203 | 14 | | GA | | 8-0 | 27-81-11 | C03014 | A2 | D | | D40250J | 3 | | | 115-199 |
| 0204 | 14 | | GA | | 7-2 | 27-81-11 | C03014 | B2 | D | | D40250J | 4 | | | 001-099 |
| 0204 | 14 | | GA | | 8-0 | 27-81-11 | C03014 | B2 | D | | D40250J | 4 | | | 115-199 |
| 0206 | 14 | | GA | | 8-0 | 24-32-11 | C00318 | A1 | D | | D40250J | 6 | | | ALL |
| 0207 | 14 | | GA | | 8-0 | 24-32-11 | C00318 | B1 | D | | D40250J | 7 | | | ALL |
| 0208 | 14 | | GA | | 8-0 | 24-32-11 | C00318 | C1 | D | | D40250J | 8 | | | ALL |
| 0209 | 14 | | GA | | 7-5 | 27-51-11 | C00323 | A2 | D | | D40250J | 9 | | | 001-099 |
| 0209 | 14 | | GA | | 8-0 | 27-51-11 | C00323 | A2 | D | | D40250J | 9 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0064 | 286N0064 | | | P6-4 MODULE WIRING - RIGHT AC BUSSES (continued) | | | | | | | | | | | |
| 0210 | 14 | | GA | | 7-5 | 27-51-11 | C00323 | B2 | D | | D40250J | 10 | | | 001-099 |
| 0210 | 14 | | GA | | 8-0 | 27-51-11 | C00323 | B2 | D | | D40250J | 10 | | | 115-199 |
| 0211 | 14 | | GA | | 7-5 | 27-51-11 | C00323 | C2 | D | | D40250J | 11 | | | 001-099 |
| 0211 | 14 | | GA | | 8-0 | 27-51-11 | C00323 | C2 | D | | D40250J | 11 | | | 115-199 |
| 0212 | 14 | | GA | | 7-2 | 27-81-11 | C03014 | C2 | D | | D40250J | 12 | | | 001-099 |
| 0212 | 14 | | GA | | 8-0 | 27-81-11 | C03014 | C2 | D | | D40250J | 12 | | | 115-199 |
| 0301 | 16 | | GA | | 7-1 | 21-58-13 | C00332 | A1 | D | | D40868J | 41 | | | 001-099 |
| 0301 | 16 | | GA | | 8-0 | 21-58-13 | C00332 | A1 | D | | D40294J | 1 | | | 115-199 |
| 0302 | 16 | | GA | | 7-1 | 21-58-13 | C00332 | B1 | D | | D40868J | 40 | | | 001-099 |
| 0302 | 16 | | GA | | 8-0 | 21-58-13 | C00332 | B1 | D | | D40294J | 2 | | | 115-199 |
| 0303 | 16 | | GA | | 7-1 | 21-58-13 | C00332 | C1 | D | | D40868J | 27 | | | 001-099 |
| 0303 | 16 | | GA | | 8-0 | 21-58-13 | C00332 | C1 | D | | D40294J | 3 | | | 115-199 |
| 0404 | 18 | | GA | | 7-0 | 25-29-11 | C03020 | A1 | D | | D40168J | 4 | | | ALL |
| 0405 | 18 | | GA | | 7-0 | 25-29-11 | C03020 | B1 | D | | D40168J | 5 | | | ALL |
| 0501 | 16 | | GA | | 8-0 | 24-51-22 | C00307 | A2 | D | * | D40248J | 1 | | | ALL |
| 0502 | 16 | | GA | | 8-0 | 24-51-22 | C00307 | B2 | D | * | D40248J | 2 | | | ALL |
| 0503 | 16 | | GA | | 8-0 | 24-51-22 | C00307 | C2 | D | * | D40248J | 3 | | | ALL |
| 0504 | 16 | | GA | | 8-0 | 24-51-21 | C00319 | C1 | D | | D40248J | 4 | | | ALL |
| 0505 | 16 | | GA | | 8-0 | 24-51-21 | C00319 | B1 | D | | D40248J | 5 | | | ALL |
| 0506 | 16 | | GA | | 8-0 | 24-51-21 | C00319 | A1 | D | | D40248J | 6 | | | ALL |
| 0507 | 12 | | HA | | 6-8 | 24-51-52 | C03007 | C1 | D | | D40248J | 7 | | | 001-099 |
| 0507 | 12 | | HA | | 6-0 | 24-51-52 | C03007 | C1 | D | | D40248J | 7 | | | 115-199 |
| 0508 | 12 | | HA | | 6-8 | 24-51-52 | C03007 | B1 | D | | D40248J | 8 | | | 001-099 |
| 0508 | 12 | | HA | | 6-0 | 24-51-52 | C03007 | B1 | D | | D40248J | 8 | | | 115-199 |
| 0509 | 12 | | HA | | 6-8 | 24-51-52 | C03007 | A1 | D | | D40248J | 9 | | | 001-099 |
| 0509 | 12 | | HA | | 6-0 | 24-51-52 | C03007 | A1 | D | | D40248J | 9 | | | 115-199 |
| 0510 | 14 | | GA | | 1-11 | 24-53-21 | D40248J | 10 | | | D40250J | 5 | | | 001-099 |
| 0510 | 14 | | GA | | 2-0 | 24-53-21 | D40248J | 10 | | | D40250J | 5 | | | 115-199 |
| 0601 | 22 | | GA | | 5-0 | 24-51-72 | D04010P | 4 | | | D42204J | 5 | | | ALL |
| 0602 | 22 | | GA | | 5-0 | 24-51-72 | D04010P | 12 | | | D42204J | 6 | | | ALL |
| 0603 | 22 | | GA | | 5-0 | 24-51-72 | D04010P | 13 | | | D42204J | 8 | | | ALL |
| 0604 | 16 | | GA | | 4-10 | 24-51-72 | C04269 | =L | D | | D04010P | 17 | | | 001-099 |
| 0604 | 16 | | GA | | 5-0 | 24-51-72 | D04010P | 17 | | | C04269 | =L | D | | 115-199 |
| 0605 | 16 | | GA | | 4-9 | 24-51-72 | C04268 | =L | D | | D04010P | 16 | | | 001-099 |
| 0605 | 16 | | GA | | 5-0 | 24-51-72 | D04010P | 16 | | | C04268 | =L | D | | 115-199 |
| 0606 | 16 | | GA | | 4-9 | 24-51-72 | C04267 | =L | D | | D04010P | 6 | | | 001-099 |
| 0606 | 16 | | GA | | 5-0 | 24-51-72 | D04010P | 6 | | | C04267 | =L | D | | 115-199 |
| 0607 | 22 | | GA | | 3-8 | 24-51-72 | D04010P | 7 | | | GD00529 | DC.. | 2 | | 001-099 |
| 0607 | 22 | | GA | | 4-0 | 24-51-72 | D04010P | 7 | | | GD00529 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0064 | 286N0064 | P6-4 MODULE WIRING - RIGHT AC BUSSES (continued) | | | | | | | | | | | | | |
| 0608 | 22 | GA | | | 3-8 | 24-51-72 | D04010P | 19 | | | GD00529 | DC.. | 2 | | 001-099 |
| 0608 | 22 | GA | | | 4-0 | 24-51-72 | D04010P | 19 | | | GD00529 | DC.. | 2 | | 115-199 |
| 0609 | 20 | GA | | | 3-8 | 24-51-72 | D04010P | 18 | | | GD00529 | ST.. | 2 | | 001-099 |
| 0609 | 20 | GA | | | 4-0 | 24-51-72 | D04010P | 18 | | | GD00529 | ST.. | 2 | | 115-199 |
| 0701 | 16 | GA | | | 10-0 | 24-51-22 | C00307 | A2 | D | * | C04267 | =B | D | | 001-099 |
| 0701 | 16 | GA | | | 3-0 | 24-51-22 | C00307 | A2 | D | * | C04267 | =B | D | | 115-199 |
| 0702 | 16 | GA | | | 10-0 | 24-51-22 | C00307 | B2 | D | * | C04268 | =B | D | | 001-099 |
| 0702 | 16 | GA | | | 3-0 | 24-51-22 | C00307 | B2 | D | * | C04268 | =B | D | | 115-199 |
| 0703 | 16 | GA | | | 10-0 | 24-51-22 | C00307 | C2 | D | * | C04269 | =B | D | | 001-099 |
| 0703 | 16 | GA | | | 3-0 | 24-51-22 | C00307 | C2 | D | * | C04269 | =B | D | | 115-199 |
| ZZAA | 02 | ZB | | | 0-0 | 24-51-23 | C04003 | =B | D | | C01135 | =B | D | | ALL |
| ZZXD | 02 | ZA | | | 0-3 | 24-51-21 | C00307 | A1 | D | | C00318 | A2 | D | | ALL |
| ZZXE | 02 | ZA | | | 0-3 | 24-51-21 | C00307 | B1 | D | | C00318 | B2 | D | | ALL |
| ZZXF | 02 | ZA | | | 0-3 | 24-51-21 | C00307 | C1 | D | | C00318 | C2 | D | | ALL |
| ZZXG | 02 | ZA | | | 0-3 | 24-51-23 | C00323 | A1 | D | | C00332 | A2 | D | | ALL |
| ZZXH | 02 | ZA | | | 0-3 | 24-51-23 | C00323 | B1 | D | | C00332 | B2 | D | | ALL |
| ZZXJ | 02 | ZA | | | 0-3 | 24-51-23 | C00323 | C1 | D | | C00332 | C2 | D | | ALL |
| W0066 | 286N0066 | P6-2 MODULE WIRING - BATTERY BUSSES | | | | | | | | | | | | | |
| 0001 | 18 | GA | | | 5-0 | 24-51-31 | C00899 | =L | D | | D00544 | A1 | | | 001-099 |
| 0001 | 16 | GA | | | 5-0 | 24-51-31 | C00899 | =L | D | | D00544 | A1 | | | 115-199 |
| 0002 | 06 | CQ | | | 0-10 | 24-33-11 | C00813 | =L | F | | K00104 | A1 | E | | ALL |
| 0003 | 08 | HA | | | 0-9 | 24-33-11 | C00898 | =L | D | | K00104 | B1 | E | | ALL |
| 0004 | 08 | HA | | | 0-10 | 24-54-72 | C00897 | =L | D | | TB5011 | 8 | E | | ALL |
| 0005 | 02 | CQ | | | 2-6 | 24-31-11 | C00896 | =L | F | | TB5009 | =1 | F | | ALL |
| 0006 | 02 | CQ | | | 2-3 | 24-31-11 | C00896 | =B | F | | TB5010 | =1 | F | | ALL |
| 0010 | 02 | CQ | | | 2-7 | 24-33-12 | C04282 | =L | F | | TB5017 | =1 | H | | 001-099 |
| 0011 | 06 | CQ | | | 3-4 | 24-31-11 | C04348 | =B | D | | C00899 | =B | D | | 001-002 |
| 0011 | 06 | CQ | | | 3-4 | 24-31-11 | C00899 | =B | D | | C04348 | =B | D | | 115-199 |
| 0012 | 06 | CQ | | | 6-6 | 24-31-11 | C04348 | =L | D | | TB5019 | 12 | E | | 001-002 |
| 0012 | 06 | CQ | | | 6-6 | 24-31-11 | C04348 | CAP | Y | | TB5019 | 12 | E | | 115-199 |
| 0013 | 06 | CQ | | | 3-4 | 24-31-11 | C00899 | =B | D | | C00550 | =B | D | | 003-099 |
| 0014 | 20 | GA | | | 13-0 | 24-31-11 | C00550 | =L | D | | D40870J | 1 | | | 003-099 |
| 0016 | 08 | HA | | | 0-5 | 24-31-11 | C00550 | =B | D | | C04348 | =B | D | | 003-099 |
| 0017 | 08 | HA | | | 6-6 | 24-31-11 | C04348 | =L | D | | TB5019 | 12 | E | | 003-099 |
| ZZOA | 00 | ZB | | | 0-0 | 24-31-11 | C00899 | =B | D | | C00813 | =B | F | | ALL |
| ZZOB | 00 | ZB | | | 0-0 | 24-31-11 | C00813 | =B | F | | C00898 | =B | D | | ALL |
| ZZOC | 00 | ZB | | | 0-0 | 24-31-11 | C00898 | =B | D | | C00897 | =B | D | | ALL |
| ZZOD | 00 | ZB | | | 0-0 | 24-31-11 | C00897 | =B | D | | C00896 | =B | F | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | Description | | From | To | | | | | | | | |
|------------|-------------|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0066 | 286N0066 | | P6-2 MODULE WIRING - BATTERY BUSSES (continued) | | | | | | | | | | | |
| ZZOE | 00 | ZB | | 0-0 | 24-31-11 | C04282 | =B | F | | C00896 | =B | F | | 001-099 |
| W0068 | 286N0068 | | P6-3 MODULE WIRING - STANDBY AC BUS | | | | | | | | | | | |
| 0001 | 14 | GA | | 4-8 | 24-33-11 | C00817 | =B | D | | TB5013 | 4 | E | | ALL |
| 0002 | 16 | GA | | 5-1 | 24-54-73 | C00892 | =B | D | * | D40244J | 2 | | | ALL |
| 0003 | 24 | GK | | 6-11 | 24-28-11 | C00817 | =L | D | | D40246J | 3 | | | ALL |
| 0004 | 22 | GA | | 10-3 | 24-51-31 | C00875 | =L | D | | D00544 | B1 | | | ALL |
| 0005 | 16 | GA | | 7-0 | 24-33-11 | C00892 | =B | D | * | D01878 | C3 | | | ALL |
| 0006 | 18 | GA | | 4-11 | 24-33-11 | D01680 | | 10 | | TB5013 | 4 | E | | ALL |
| 0007 | 22 | GA | | 6-3 | 24-33-11 | C00892 | =L | D | | D01682 | X1 | | | ALL |
| ZZAA | 02 | ZB | | 0-0 | 24-33-11 | C00817 | =B | D | | C00875 | =B | D | | ALL |
| W0069 | 286N0069 | | FLIGHT RECORDER CONTROL, P61 | | | | | | | | | | | |
| 0001 | 22 | GA | | 4-0 | 31-31-01 | D00009 | | 13 | | D40003J | 1 | | | 001-099 |
| 0001 | 22 | GA | | 3-0 | 31-31-12 | D40003J | | 1 | | SM00011 | | WI | | 115-199 |
| 0002 | 22 | GA | | 4-0 | 31-31-01 | D00009 | | 12 | | D40003J | 2 | | | 001-099 |
| 0002 | 22 | GA | | 3-0 | 31-31-12 | D40003J | | 2 | | D02880 | R | | | 115-199 |
| 0003 | 24 | GK | | 4-0 | 31-31-01 | D00009 | | 15 | | D40003J | 31 | | | 001-099 |
| 0003 | 24 | GK | | 3-0 | 31-31-12 | D40003J | | 31 | | D02880 | A- | | | 115-199 |
| 0004 | 22 | GA | | 3-0 | 31-31-12 | D40003J | | 4 | | D02880 | Z | | | 115-199 |
| 0005 | 24 | GK | | 4-0 | 31-31-01 | D00009 | | 9 | | D40003J | 5 | | | 001-099 |
| 0005 | 24 | GK | | 3-0 | 31-31-12 | D40003J | | 5 | | D02880 | K | | | 115-199 |
| 0006 | 24 | GK | | 4-0 | 31-31-01 | D00009 | | 6 | | D40003J | 6 | | | 001-099 |
| 0006 | 24 | GK | | 3-0 | 31-31-12 | D40003J | | 6 | | D02880 | B- | | | 115-199 |
| 0007 | 22 | GA | | 4-0 | 31-31-12 | D02880 | | X | | SM00011 | | WI | | 115-199 |
| 0011 | 22 | GA | | 4-0 | 31-31-01 | D00761 | | 11 | | D40003J | 22 | | | 001-099 |
| 0011 | 22 | GA | | 4-0 | 31-31-12 | D40003J | | 22 | | D00761 | 11 | | | 115-199 |
| 0012 | 24 | GK | | 4-0 | 31-31-01 | D00761 | | 14 | | D40003J | 23 | | | 001-099 |
| 0012 | 24 | GK | | 3-0 | 31-31-12 | D40003J | | 23 | | SM00009 | | WI | | 115-199 |
| 0013 | 24 | GK | | 4-0 | 31-31-01 | D00761 | | 15 | | D40003J | 24 | | | 001-099 |
| 0013 | 24 | GK | | 3-0 | 31-31-12 | D40003J | | 24 | | SM00010 | | WI | | 115-199 |
| 0014 | 24 | GK | | 4-0 | 31-31-12 | D00761 | | 14 | | SM00009 | | WI | | 115-199 |
| 0015 | 24 | GK | | 4-0 | 31-31-12 | D00761 | | 15 | | SM00010 | | WI | | 115-199 |
| 0021 | 24 | GK | | 3-0 | 31-31-12 | D40003J | | 21 | | D02880 | J- | | | 115-199 |
| 0024 | 22 | GA | | 4-0 | 31-31-01 | D00009 | | 11 | | D00761 | 2 | | | 001-099 |
| 0024 | 22 | GA | | 5-0 | 31-31-12 | D00761 | | 2 | | TB0121Y | C001 | BJ | | 115-199 |
| 0025 | 22 | GA | | 4-0 | 31-31-01 | D00009 | | 5 | | D00761 | 1 | | | 001-099 |
| 0025 | 22 | GA | | 4-0 | 31-31-12 | D00761 | | 1 | | SM00011 | | WI | | 115-199 |
| 0026 | 20 | GA | | 3-0 | 31-31-01 | D00761 | | 10 | | GD02607 | AC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0069 | 286N0069 | FLIGHT RECORDER CONTROL, P61 (continued) | | | | | | | | | | | | | |
| 0026 | 20 | GA | | | 5-0 | 31-31-12 | D00761 | 10 | | | GD00619 | AC.. | 2 | | 115-199 |
| 0027 | 20 | GA | | | 1-6 | 31-31-01 | D00761 | | | AA | GD02607 | ST.. | 2 | | 001-099 |
| 0028 | 20 | GA | | | 3-0 | 31-31-01 | D00009 | 7 | | | GD02607 | ST.. | 2 | | 001-099 |
| 0029 | 20 | GA | | | 3-0 | 31-31-01 | D00009 | 14 | | | GD02607 | DC.. | 2 | | 001-099 |
| 0044 | 22 | GA | | | 5-0 | 31-31-12 | D02880 | Y | | | TB0121Y | C001 | BJ | | 115-199 |
| 0046 | 24 | GK | | | 4-0 | 31-31-12 | D02880 | C- | | | SM00009 | | WI | | 115-199 |
| 0047 | 24 | GK | | | 4-0 | 31-31-12 | D02880 | D- | | | SM00010 | | WI | | 115-199 |
| 0060 | 20 | GA | | | 5-0 | 31-31-12 | D02880 | S | | | GD00619 | AC.. | 2 | | 115-199 |
| 0061 | 20 | GA | | | 5-0 | 31-31-12 | D02880 | S- | | | GD00619 | DC.. | 2 | | 115-199 |
| 0062 | 20 | GA | | | 5-0 | 31-31-12 | D02880 | T- | | | GD00619 | ST.. | 2 | | 115-199 |
| 0063 | 20 | GA | | | 4-0 | 33-13-71 | D02880 | F- | | | TB0121Z | 9 | BJ | | 115-199 |
| 0064 | 20 | GA | | | 5-0 | 33-13-71 | D02880 | G- | | | GD00619 | AC.. | 2 | | 115-199 |
| 0065 | 22 | GA | | | 4-0 | 33-16-13 | D02880 | L | | | TB0121Z | 10 | BJ | | 115-199 |
| 0066 | 22 | GA | | | 4-0 | 33-16-13 | D02880 | M | | | TB0121Z | 15 | BJ | | 115-199 |
| 0067 | 22 | GA | | | 5-0 | 33-16-13 | D00009 | 3 | | | TB0121Z | 10 | BJ | | 001-099 |
| 0068 | 22 | GA | | | 5-0 | 33-16-13 | D00009 | 4 | | | TB0121Z | 15 | BJ | | 001-099 |
| 5001B | 24 | G2 | AA | | 4-0 | SPARE | D00761 | 13 | | | D40003J | 11 | | | 001-099 |
| 5001B | 24 | G2 | AA | | 4-0 | 31-31-12 | D40003J | 11 | | | SM00002 | | WI | | 115-199 |
| 5001R | 24 | G2 | AA | | 0-0 | SPARE | D00761 | 12 | | | D40003J | 10 | | | 001-099 |
| 5001R | 24 | G2 | AA | | 0-0 | 31-31-12 | D40003J | 10 | | | SM00001 | | WI | | 115-199 |
| 5001Z | | | AA | | 0-0 | SPARE | D00761 | | | AA | D40003J | 7 | | | 001-099 |
| 5001Z | | | AA | | 0-0 | 31-31-12 | D40003J | 7 | | | SM00REF | 1 | | AA | 115-199 |
| 5002B | 24 | G2 | AB | | 4-0 | 31-31-01 | D00761 | 5 | | | D40003J | 15 | | | 001-099 |
| 5002B | 24 | G2 | AB | | 3-0 | 31-31-12 | D40003J | 15 | | | SM00004 | | WI | | 115-199 |
| 5002R | 24 | G2 | AB | | 0-0 | 31-31-01 | D00761 | 4 | | | D40003J | 14 | | | 001-099 |
| 5002R | 24 | G2 | AB | | 0-0 | 31-31-12 | D40003J | 14 | | | SM00003 | | WI | | 115-199 |
| 5002Z | | | AB | | 0-0 | 31-31-01 | D00761 | | | AA | D40003J | 32 | | | 001-099 |
| 5002Z | | | AB | | 0-0 | 31-31-12 | D40003J | 32 | | | SM00REF | 3 | | AB | 115-199 |
| 5003B | 24 | G2 | AC | | 4-0 | SPARE | D00761 | 7 | | | D40003J | 17 | | | 001-099 |
| 5003B | 24 | G2 | AC | | 3-0 | 31-31-12 | D40003J | 17 | | | SM00006 | | WI | | 115-199 |
| 5003R | 24 | G2 | AC | | 0-0 | SPARE | D00761 | 6 | | | D40003J | 16 | | | 001-099 |
| 5003R | 24 | G2 | AC | | 0-0 | 31-31-12 | D40003J | 16 | | | SM00005 | | WI | | 115-199 |
| 5003Z | | | AC | | 0-0 | SPARE | D00761 | | | AA | D40003J | 33 | | | 001-099 |
| 5003Z | | | AC | | 0-0 | 31-31-12 | D40003J | 33 | | | SM00REF | 5 | | AC | 115-199 |
| 5004B | 24 | G2 | AD | | 4-0 | 31-31-01 | D00761 | 9 | | | D40003J | 9 | | | 001-099 |
| 5004B | 24 | G2 | AD | | 4-0 | 31-31-12 | D00761 | 13 | | | SM00002 | | WI | | 115-199 |
| 5004R | 24 | G2 | AD | | 0-0 | 31-31-01 | D00761 | 8 | | | D40003J | 8 | | | 001-099 |
| 5004R | 24 | G2 | AD | | 0-0 | 31-31-12 | D00761 | 12 | | | SM00001 | | WI | | 115-199 |
| 5004Z | | | AD | | 0-0 | 31-31-01 | D00761 | | | AA | D40003J | 41 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0060

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0069 | 286N0069 | | | FLIGHT RECORDER CONTROL, P61 (continued) | | | | | | | | | | | | |
| 5004Z | | | | AD | 0-0 | 31-31-12 | D00761 | | | | AD | SM00REF | 1 | | AA | 115-199 |
| 5005B | 24 | G2 | AE | | 4-0 | 31-31-12 | D00761 | | 5 | | | SM00004 | | WI | | 115-199 |
| 5005R | 24 | G2 | AE | | 0-0 | 31-31-12 | D00761 | | 4 | | | SM00003 | | WI | | 115-199 |
| 5005Z | | | AE | | 0-0 | 31-31-12 | D00761 | | | | AD | SM00REF | 3 | | AB | 115-199 |
| 5006B | 24 | G2 | AF | | 4-0 | 31-31-12 | D00761 | | 7 | | | SM00006 | | WI | | 115-199 |
| 5006R | 24 | G2 | AF | | 0-0 | 31-31-12 | D00761 | | 6 | | | SM00005 | | WI | | 115-199 |
| 5006Z | | | AF | | 0-0 | 31-31-12 | D00761 | | | | AD | SM00REF | 5 | | AC | 115-199 |
| 5010B | 24 | G2 | AG | | 4-0 | 31-31-12 | D02880 | | F | | | SM00002 | | WI | | 115-199 |
| 5010R | 24 | G2 | AG | | 0-0 | 31-31-12 | D02880 | | E | | | SM00001 | | WI | | 115-199 |
| 5010Z | | | AG | | 0-0 | 31-31-12 | D02880 | | DED | | | SM00REF | 1 | | AA | 115-199 |
| 5011B | 24 | G2 | AH | | 4-0 | 31-31-12 | D02880 | | H | | | SM00004 | | WI | | 115-199 |
| 5011R | 24 | G2 | AH | | 0-0 | 31-31-12 | D02880 | | G | | | SM00003 | | WI | | 115-199 |
| 5011Z | | | AH | | 0-0 | 31-31-12 | D02880 | | DED | | | SM00REF | 3 | | AB | 115-199 |
| 5012B | 24 | G2 | AI | | 4-0 | 31-31-12 | D02880 | | D | | | SM00006 | | WI | | 115-199 |
| 5012R | 24 | G2 | AI | | 0-0 | 31-31-12 | D02880 | | C | | | SM00005 | | WI | | 115-199 |
| 5012Z | | | AI | | 0-0 | 31-31-12 | D02880 | | DED | | | SM00REF | 5 | | AC | 115-199 |
| 5013B | 24 | G2 | AJ | | 4-0 | 31-31-12 | D40003J | | 9 | | | D00761 | 9 | | | 115-199 |
| 5013R | 24 | G2 | AJ | | 0-0 | 31-31-12 | D40003J | | 8 | | | D00761 | 8 | | | 115-199 |
| 5013Z | | | AJ | | 0-0 | 31-31-12 | D40003J | | 41 | | | GD02607 | ST.. | 2 | | 115-199 |
| FRAA | | | | | 0-0 | 31-31-01 | D00761 | | | | AA | D00761 | 3 | | | 001-099 |
| FRAA | | | | | 0-0 | 31-31-12 | GD00619 | | ST.. | 2 | | SM00REF | 1 | | AA | 115-199 |
| FRAB | | | | | 0-0 | 31-31-12 | GD00619 | | ST.. | 2 | | SM00REF | 3 | | AB | 115-199 |
| FRAC | | | | | 0-0 | 31-31-12 | GD00619 | | ST.. | 2 | | SM00REF | 5 | | AC | 115-199 |
| FRAD | | | | | 0-0 | 31-31-12 | D00761 | | | | AD | D00761 | 3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11
Section W0060
Page 15 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0070 | 286N0070 | | | P6-2 MODULE WIRING - RIGHT DC BUSES | | | | | | | | | | | |
| 0001 | 02 | | CQ | | 3-0 | 24-32-11 | C00889 | =B | F | | TB5007 | =1 | F | | ALL |
| 0002 | 04 | | CQ | | 2-3 | 24-32-11 | C00889 | =L | F | | K00108 | A2 | F | | ALL |
| 0004 | 08 | | HA | | 2-5 | 24-54-21 | C00890 | =L | D | | TB5011 | 4 | E | | ALL |
| 0005 | 08 | | HA | | 2-5 | 24-54-21 | C00891 | =L | D | | TB5011 | 5 | E | | ALL |
| 0006 | 22 | | GA | | 5-0 | 24-34-11 | C04143 | =L | D | * | D01856 | 6 | | | ALL |
| 0008 | 22 | | GA | | 3-11 | 24-34-11 | C04143 | =L | D | * | D40286J | 8 | | | ALL |
| 0009 | 18 | | GA | | 2-2 | 25-29-11 | C04234 | =L | D | | D04020 | Y | C | | ALL |
| 0010 | 18 | | GA | | 2-8 | 25-29-11 | D04020 | X | C | | GD00528 | DC.. | 2 | | ALL |
| 0011 | 22 | | GA | | 4-1 | 24-32-41 | C00865 | =L | D | | D40286J | 11 | | | ALL |
| ZZAB | 00 | | ZB | | 0-0 | 24-54-21 | C00865 | =B | D | | C04234 | =B | D | | 001-099 |
| ZZAC | 03 | | ZB | | 0-0 | 24-54-21 | C00865 | =B | D | | C04143 | =B | D | | ALL |
| ZZAD | 00 | | ZB | | 0-0 | 24-54-21 | C04234 | =B | D | | C04143 | =B | D | | 001-099 |
| ZZOA | 00 | | ZB | | 0-0 | 24-32-11 | C00891 | =B | D | | C00890 | =B | D | | ALL |
| ZZOB | 00 | | ZB | | 0-0 | 24-32-11 | C00889 | =B | F | | C00891 | =B | D | | ALL |
| ZZOD | 00 | | ZB | | 0-0 | 24-54-21 | C04143 | =B | D | | C04234 | =B | D | | 115-199 |
| ZZOE | 00 | | ZB | | 0-0 | 24-54-21 | C04234 | =B | D | | C00865 | =B | D | | 115-199 |
| ZZXB | 02 | | ZA | | 0-0 | 24-54-21 | C00890 | =L | D | | C04143 | =B | D | | ALL |
| W0072 | 286N0072 | | | P6-2 MODULE WIRING - LEFT DC BUSES | | | | | | | | | | | |
| 0001 | 02 | | CQ | | 1-11 | 24-32-11 | C00881 | =B | F | | TB5008 | =1 | F | | ALL |
| 0002 | 08 | | HA | | 3-6 | 24-54-11 | C00883 | =L | D | | TB5011 | 2 | E | | ALL |
| 0004 | 22 | | GA | | 3-8 | 24-34-11 | C04142 | =L | D | | D01856 | 4 | | | ALL |
| 0005 | 08 | | HA | | 1-10 | 24-33-11 | C00886 | =L | D | * | K00106 | B1 | E | | ALL |
| 0006 | 08 | | HA | | 1-8 | 24-33-11 | C00885 | =L | D | | K00106 | A1 | E | | ALL |
| 0007 | 22 | | GA | | 5-1 | 24-34-11 | C04142 | =L | D | | D40286J | 7 | | | ALL |
| 0008 | 04 | | CQ | | 2-0 | 24-32-11 | C00881 | =L | F | | K00108 | A1 | F | | ALL |
| 0009 | 08 | | HA | | 3-6 | 24-54-11 | C00882 | =L | D | | TB5011 | 1 | E | | ALL |
| 0010 | 18 | | GA | | 2-9 | 24-51-31 | C00884 | =L | D | | D00544 | A3 | | | ALL |
| 0011 | 22 | | GA | | 3-8 | 24-33-11 | C00887 | =L | D | * | D00546 | 6 | | | ALL |
| 0012 | 22 | | GA | | 3-8 | 24-33-11 | C00887 | =L | D | * | D00546 | 1 | | | ALL |
| 0018 | 16 | | GA | | 5-0 | 78-34-51 | C04472 | =L | D | | D40284J | 5 | 16 | | 001-002, 115-199 |
| 0018 | 16 | | GA | | 3-10 | 78-34-51 | C04472 | =L | D | | D40284J | 5 | 16 | | 003-099 |
| 0019 | 12 | | HA | | 1-2 | 24-32-11 | C00886 | =L | D | * | C04142 | =B | D | | ALL |
| 0021 | 16 | | GA | | 6-0 | 78-34-61 | C04474 | =L | D | | D40286J | 5 | 16 | | 001-002, 115-199 |
| 0021 | 16 | | GA | | 5-1 | 78-34-61 | C04474 | =L | D | | D40286J | 5 | 16 | | 003-099 |
| 0022 | 14 | | GA | | 11-0 | 24-54-71 | C04137 | =B | D | | C04472 | =B | D | | 001-002, 115-199 |
| 0022 | 14 | | GA | | 5-2 | 24-54-71 | C04137 | =B | D | | C04472 | =B | D | * | 003-099 |
| 0023 | 16 | | GA | | 2-0 | 24-54-71 | C04472 | =B | D | | C04474 | =B | D | | 001-002, 115-199 |
| 0023 | 16 | | GA | | 1-6 | 24-54-71 | C04472 | =B | D | * | C04474 | =B | D | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W0070

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0072 | 286N0072 | | | P6-2 MODULE WIRING - LEFT DC BUSSES (continued) | | | | | | | | | | | |
| 4001B | 24 | GN | AA | | 2-11 | 24-23-11 | D02164 | | 3 | | D40284J | 3 | | | ALL |
| 4001G | 24 | GN | AA | | 0-0 | 24-23-11 | D02164 | | 4 | | D40284J | 4 | | | ALL |
| 4001R | 24 | GN | AA | | 0-0 | 24-23-11 | D02164 | | 1 | | D40284J | 1 | | | ALL |
| 4001Y | 24 | GN | AA | | 0-0 | 24-23-11 | D02164 | | 2 | | D40284J | 2 | | | ALL |
| ZZCC | 03 | ZB | | | 0-0 | 24-32-11 | C04142 | =B | D | | C00884 | =B | D | | ALL |
| ZZDD | 00 | ZB | | | 0-0 | 24-32-11 | C00884 | =B | D | | C00887 | =B | D | | ALL |
| ZZEE | 00 | ZB | | | 0-0 | 24-32-11 | C00887 | =B | D | | C04142 | =B | D | | ALL |
| ZZOA | 00 | ZB | | | 0-0 | 24-32-11 | C00886 | =B | D | | C00885 | =B | D | | ALL |
| ZZOB | 00 | ZB | | | 0-0 | 24-32-11 | C00885 | =B | D | | C00881 | =B | F | | ALL |
| ZZOC | 00 | ZB | | | 0-0 | 24-32-11 | C00882 | =B | D | | C00883 | =B | D | | ALL |
| ZZOD | 00 | ZB | | | 0-0 | 24-32-11 | C00881 | =B | F | | C00882 | =B | D | | ALL |
| W0074 | 286N0074 | | | P6 MODULE WIRING - STANDBY AND BATTERY BUSSES | | | | | | | | | | | |
| 0001 | 18 | GA | | | 6-10 | 24-33-11 | D01878 | | C2 | | D01680 | 7 | | | ALL |
| 0002 | 22 | GA | | | 2-0 | 24-33-11 | K00104 | X2 | C | | K00106 | 13 | C | | ALL |
| 0003 | 08 | HA | | | 1-11 | 24-54-71 | TB5011 | 3 | E | | K00106 | B2 | E | | ALL |
| 0004 | 08 | HA | | | 1-0 | 24-33-11 | K00104 | A2 | E | | K00106 | A2 | E | | ALL |
| 0005 | 08 | HA | | | 0-10 | 24-33-11 | K00104 | B2 | E | | K00106 | B2 | E | | ALL |
| 0006 | 22 | GA | | | 3-5 | 24-33-11 | D00548 | B2 | | | K00106 | X2 | C | | ALL |
| 0008 | 20 | GA | | | 1-6 | 24-33-11 | D00546 | | 2 | | GD00528 | DC.. | 2 | | ALL |
| 0009 | 22 | GA | | | 3-5 | 24-51-72 | K00108 | X2 | C | | D00548 | D2 | | | ALL |
| 0010 | 22 | GA | | | 3-2 | 24-31-11 | TB0024Y | A001 | BJ | | D01786 | X2 | | | 001-002, 115-199 |
| 0010 | 22 | GA | | | 3-2 | 24-31-11 | TB0024Y | A001 | BJ | | D01786 | X2 | | * | 003-099 |
| 0011 | 22 | GA | | | 4-11 | 24-51-72 | D01856 | | 8 | | D00548 | D3 | | | ALL |
| 0012 | 18 | GA | | | 7-9 | 24-33-11 | D01680 | | 2 | 18 | D00548 | A2 | | | ALL |
| 0013 | 20 | GA | | | 5-2 | 34-21-11 | D00145 | X1 | | | D00548 | C3 | | | 001-099 |
| 0013 | 20 | GA | | | 5-2 | 34-21-21 | D00145 | X1 | | | D00548 | C3 | | | 115-199 |
| 0014 | 20 | GA | | | 1-8 | 24-31-11 | K00104 | | 14 | C | GD00528 | DC.. | 2 | | ALL |
| 0015 | 20 | GA | | | 1-9 | 24-34-11 | D01856 | | 5 | | GD00528 | ST.. | 2 | | ALL |
| 0016 | 20 | GA | | | 1-9 | 24-34-11 | D01856 | | 7 | | GD00528 | DC.. | 2 | | ALL |
| 0017 | 20 | GA | | | 2-8 | 34-21-11 | D00145 | X2 | | | GD00528 | DC.. | 2 | | 001-099 |
| 0017 | 20 | GA | | | 2-8 | 34-21-21 | D00145 | X2 | | | GD00528 | DC.. | 2 | | 115-199 |
| 0018 | 22 | GA | | | 3-10 | 24-33-11 | D00546 | | 5 | | K00106 | X1 | C | | ALL |
| 0019 | 22 | GA | | | 3-4 | 24-33-11 | D01682 | A2 | | | TB0024Y | C001 | BJ | | ALL |
| 0020 | 22 | GA | | | 3-3 | 24-33-11 | D01678 | A2 | | | TB0024Y | C001 | BJ | | ALL |
| 0021 | 20 | GA | | | 2-11 | 24-33-11 | D01682 | A3 | | | GD00528 | DC.. | 2 | | ALL |
| 0022 | 20 | GA | | | 2-11 | 24-33-11 | D01682 | X2 | | | GD00528 | AC.. | 2 | | ALL |
| 0023 | 20 | GA | | | 2-10 | 24-33-11 | D01678 | A3 | | | GD00528 | DC.. | 2 | | ALL |
| 0024 | 20 | GA | | | 2-10 | 24-33-11 | D01678 | X2 | | | GD00528 | DC.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0070

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|-------|---------|------|-------------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W0074 | 286N0074 | | | P6 MODULE WIRING - STANDBY AND BATTERY BUSSES (continued) | | | | | | | | | | | | |
| 0025 | 20 | GA | | | 4-7 | 24-51-31 | D00548 | | X2 | | | GD00528 | DC.. | 2 | | ALL |
| 0026 | 22 | GA | | | 3-7 | 24-51-31 | D00548 | | C2 | | | K00104 | 12 | C | | ALL |
| 0027 | 22 | GA | | | 1-5 | 24-51-31 | D00548 | | C1 | | | M00540 | = A | C | | ALL |
| 0028 | 22 | GA | | | 1-2 | 24-51-31 | M00540 | | =B | C | | D00544 | X1 | | | ALL |
| 0029 | 20 | GA | | | 4-6 | 24-51-31 | D00544 | | X2 | | | GD00528 | DC.. | 2 | | ALL |
| 0030 | 20 | GA | | | 3-3 | 24-51-72 | K00108 | | 12 | C | | GD00528 | DC.. | 2 | | ALL |
| 0031 | 22 | GA | | | 3-9 | 24-34-11 | D01856 | | 11 | | | K00108 | X1 | C | * | ALL |
| 0033 | 22 | GA | | | 4-4 | 24-51-72 | D04118P | | 10 | | | D40296J | 29 | | | ALL |
| 0034 | 22 | GA | | | 3-6 | 24-51-72 | D04118P | | 3 | | | D40246J | 32 | | | ALL |
| 0035 | 24 | GK | | | 4-5 | 24-33-12 | D00542 | | D2 | | | D41904J | 9 | | | 001-099 |
| 0036 | 24 | GK | | | 5-3 | 24-33-12 | D00542 | | D3 | | | D04770 | 6 | | | 001-099 |
| 0037 | 20 | GA | | | 4-11 | 24-33-12 | D00542 | | A2 | | | GD00529 | DC.. | 2 | | 001-099 |
| 0038 | 24 | GK | | | 5-3 | 24-33-12 | D00542 | | A3 | | | D04770 | 2 | | | 001-099 |
| 0039 | 24 | GK | | | 3-7 | 24-33-12 | D04770 | | 5 | | | D41904J | 12 | | | 001-099 |
| 0041 | 24 | GK | | | 3-7 | 24-33-12 | D04770 | | 8 | | | D41904J | 11 | | | 001-099 |
| 0042 | 24 | GK | | | 3-7 | 24-33-12 | D04770 | | 1 | | | D41904J | 10 | | | 001-099 |
| 0043 | 24 | GK | | | 2-10 | 24-33-12 | D04770 | | 7 | | | K00104 | X1 | C | | 001-099 |
| 0044 | 24 | GK | | | 3-4 | 24-33-12 | D04770 | | 3 | | | K00104 | X2 | C | | 001-099 |
| 0045 | 24 | GK | | | 3-6 | 24-33-12 | D05088 | | 6 | | | D40246J | 15 | | | 001-099 |
| 0046 | 22 | GA | | | 4-10 | 24-34-11 | D00542 | | C2 | | | TB0024Y | A007 | BJ | | ALL |
| 0047 | 22 | GA | | | 2-11 | 24-34-11 | D05090 | | X1 | | | TB0024Y | A007 | BJ | | ALL |
| 0048 | 22 | GA | | | 2-10 | 24-34-11 | D05088 | | 2 | | | TB0024Y | A007 | BJ | | ALL |
| 0049 | 22 | GA | | | 2-10 | 24-34-11 | D05088 | | 5 | | | TB0024Y | C007 | BJ | | ALL |
| 0050 | 22 | GA | | | 2-10 | 24-34-11 | D05088 | | 1 | | | TB0024Y | C007 | BJ | | 001-099 |
| 0051 | 22 | GA | | | 2-10 | 24-34-11 | D05088 | | 4 | | | TB0024Y | A008 | BJ | | ALL |
| 0052 | 22 | GA | | | 2-10 | 24-34-11 | D05088 | | 8 | | | TB0024Y | A008 | BJ | | 001-099 |
| 0055 | 22 | GA | | | 0-7 | 24-31-11 | D05090 | | A2 | | | D05090 | X2 | | | ALL |
| 0056 | 22 | GA | | | 6-4 | 24-33-11 | D01680 | | 6 | | | K00106 | 12 | C | * | ALL |
| 0057 | 22 | GA | | | 3-7 | 24-33-11 | K00106 | | 12 | C | * | TB0024Y | C001 | BJ | | ALL |
| 0058 | 22 | GA | | | 6-4 | 24-33-11 | K00106 | | 11 | C | * | D01680 | 5 | | | ALL |
| 0059 | 22 | GA | | | 3-0 | 24-33-11 | K00106 | | 11 | C | * | D40296J | 34 | | | ALL |
| 0061 | 22 | GA | | | 3-5 | 24-33-11 | D40296J | | 33 | | | D05090 | A1 | | | ALL |
| 0062 | 22 | GA | | | 3-5 | 24-33-11 | D40296J | | 32 | | | D05090 | B3 | | | ALL |
| 0064 | 22 | GA | | | 2-10 | 24-34-11 | D05088 | | 7 | | | TB0024Y | C007 | BJ | | ALL |
| 0065 | 22 | GA | | | 3-2 | 24-34-11 | D40286J | | 12 | | | TB0024Y | C007 | BJ | | ALL |
| 0066 | 20 | GA | | | 2-7 | 24-34-11 | D05088 | | 3 | | | GD00528 | DC.. | 2 | | ALL |
| 0067 | 24 | GK | | | 3-7 | 24-33-12 | D04770 | | 4 | | | D41904J | 4 | | | 001-099 |
| 0068 | 22 | GA | | | 3-3 | 24-31-11 | TB0024Y | A001 | BJ | | | D40296J | 38 | | | 001-002, 115-199 |
| 0069 | 16 | GA | | | 2-8 | 34-21-21 | D00145 | | B3 | | | TB5011 | 6 | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0070

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0074 | 286N0074 | | | P6 MODULE WIRING - STANDBY AND BATTERY BUSSES (continued) | | | | | | | | | | | |
| 0085 | 24 | | GK | | 3-6 | 24-25-11 | D40296J | 38 | | | D01786 | X2 | | * | 003-099 |
| 0122 | 20 | | GA | | 4-5 | 24-31-11 | D40868J | 22 | | | D01786 | A3 | | | ALL |
| 0123 | 20 | | GA | | 4-5 | 24-31-11 | D40868J | 23 | | | D01786 | B3 | | | ALL |
| 0124 | 20 | | GA | | 4-5 | 24-31-11 | D40868J | 24 | | | D01786 | C3 | | | ALL |
| 0201 | 16 | | GA | | 2-8 | 34-21-21 | TB5011 | 6 | E | | D00145 | B3 | | | 001-099 |
| 0221 | 22 | | GA | | 3-3 | 24-34-11 | D40246J | 21 | | | K00108 | 11 | C | * | ALL |
| 0225 | 22 | | GA | | 3-3 | 24-34-11 | D40296J | 35 | | | TB0024Y | A002 | BJ | | ALL |
| 0226 | 22 | | GA | | 3-7 | 24-34-11 | D40246J | 26 | | | D05090 | B2 | | | ALL |
| 0301 | 22 | | GA | | 2-10 | 24-33-11 | D40296J | 2 | | | K00106 | 14 | C | | ALL |
| 0302 | 18 | | GA | | 4-5 | 24-33-11 | D40296J | 28 | 18 | | D00548 | A3 | | | ALL |
| 0303 | 22 | | GA | | 3-6 | 24-33-11 | D40296J | 4 | | | D01878 | X2 | | | ALL |
| 0304 | 22 | | GA | | 3-3 | 24-33-11 | D40296J | 6 | | | TB0024Y | A002 | BJ | | ALL |
| 0305 | 22 | | GA | | 3-3 | 24-33-11 | D40296J | 5 | | | TB0024Y | C001 | BJ | | ALL |
| 0306 | 22 | | GA | | 3-3 | 24-31-11 | D40296J | 7 | | | TB0024Y | A001 | BJ | | ALL |
| 0307 | 22 | | GA | | 3-2 | 24-34-11 | D40296J | 8 | | | K00108 | X1 | C | * | ALL |
| 0308 | 22 | | GA | | 4-5 | 24-33-11 | D40296J | 3 | | | D00548 | B3 | | | ALL |
| 0401 | 20 | | GA | | 3-8 | 24-31-11 | D40282J | 1 | | | D01786 | A2 | | | ALL |
| 0402 | 20 | | GA | | 3-8 | 24-31-11 | D40282J | 2 | | | D01786 | B2 | | | ALL |
| 0403 | 20 | | GA | | 3-8 | 24-31-11 | D40282J | 3 | | | D01786 | C2 | | | ALL |
| 0404 | 22 | | GA | | 2-10 | 24-31-11 | D40282J | 4 | | | K00104 | 13 | C | | ALL |
| 0405 | 22 | | GA | | 3-7 | 24-34-11 | D40282J | 5 | | | D05090 | B1 | | | ALL |
| 0406 | 22 | | GA | | 3-5 | 24-31-11 | D40282J | 6 | | | TB0024Y | A001 | BJ | | ALL |
| 0407 | 22 | | GA | | 4-7 | 24-34-11 | D40282J | 7 | | | D00542 | C3 | | | ALL |
| 0408 | 22 | | GA | | 3-7 | 24-31-11 | D40282J | 8 | | | D05090 | A3 | | | ALL |
| 0409 | 22 | | GA | | 3-5 | 24-34-11 | D40282J | 9 | | | TB0024Y | A002 | BJ | | ALL |
| 0501 | 22 | | GA | | 3-4 | 24-51-72 | D00544 | D3 | | | K00108 | 13 | C | | ALL |
| 0502 | 24 | | GK | | 4-10 | 24-51-31 | TB0024Y | C010 | BJ | | D00542 | X1 | | | 001-099 |
| 0502 | 22 | | GA | | 4-10 | 24-51-31 | TB0024Y | C010 | BJ | | D00542 | X1 | | | 115-199 |
| 0503 | 24 | | GK | | 4-10 | 24-51-31 | TB0024Y | C010 | BJ | | D00542 | B1 | | | 001-099 |
| 0503 | 22 | | GA | | 4-10 | 24-51-31 | TB0024Y | C010 | BJ | | D00542 | B1 | | | 115-199 |
| 0504 | 24 | | GK | | 5-0 | 24-51-31 | TB0024Y | C002 | BJ | | D00542 | B2 | | | 001-099 |
| 0504 | 22 | | GA | | 5-0 | 24-51-31 | TB0024Y | C002 | BJ | | D00542 | B2 | | | 115-199 |
| 0525 | 22 | | GA | | 3-4 | 24-51-72 | D00544 | D1 | | | K00108 | 11 | C | * | ALL |
| 0600 | 22 | | GA | | 0-7 | 24-51-31 | D00544 | B2 | | | D00544 | C2 | | | ALL |
| 0601 | 24 | | GK | | 3-0 | 24-51-31 | D40298J | 1 | | | TB0024Y | C010 | BJ | | 001-099 |
| 0601 | 22 | | GA | | 3-0 | 24-51-31 | D40298J | 1 | | | TB0024Y | C010 | BJ | | 115-199 |
| 0602 | 22 | | GA | | 3-0 | 24-51-31 | D40298J | 2 | | | TB0024Y | A009 | BJ | | ALL |
| 0603 | 18 | | GA | | 4-3 | 24-51-31 | D40298J | 3 | | | D00544 | A2 | | | ALL |
| 0604 | 22 | | GA | | 4-9 | 24-51-31 | D00544 | C3 | | | TB0024Y | A009 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0070

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0074 | 286N0074 | | | P6 MODULE WIRING - STANDBY AND BATTERY BUSSES (continued) | | | | | | | | | | | |
| 0605 | 22 | GA | | | 4-9 | 24-51-31 | D00544 | | C1 | | TB0024Y | A009 | BJ | | ALL |
| 0701 | 22 | GA | | | 4-8 | 22-11-32 | D40300J | | 1 | | D00542 | X2 | | | ALL |
| 0702 | 22 | GA | | | 4-7 | 22-11-32 | D04118P | | 5 | | D40300J | 2 | | | ALL |
| 0703 | 24 | GK | | | 3-6 | 24-51-31 | D40300J | | 3 | | TB0024Y | C002 | BJ | | 001-099 |
| 0703 | 22 | GA | | | 3-6 | 24-51-31 | D40300J | | 3 | | TB0024Y | C002 | BJ | | 115-199 |
| 0704 | 24 | GK | | | 4-8 | 24-51-31 | D40300J | | 4 | | D00548 | X1 | | | 001-099 |
| 0704 | 22 | GA | | | 4-8 | 24-51-31 | D40300J | | 4 | | D00548 | X1 | | | 115-199 |
| 0705 | 24 | GK | | | 3-6 | 24-51-31 | D40300J | | 5 | | TB0024Y | C002 | BJ | | 001-099 |
| 0705 | 22 | GA | | | 3-6 | 24-51-31 | D40300J | | 5 | | TB0024Y | C002 | BJ | | 115-199 |
| 0710 | 22 | GA | | | 3-5 | 24-51-72 | D04010P | | 2 | | D42206J | 6 | | | ALL |
| 0711 | 22 | GA | | | 3-5 | 24-51-72 | D04010P | | 8 | | D42206J | 5 | | | ALL |
| 0712 | 22 | GA | | | 3-5 | 24-51-72 | D04010P | | 9 | | D42206J | 8 | | | ALL |
| 0713 | 22 | GA | | | 3-3 | 24-51-72 | D04010P | | 3 | | D40246J | 31 | | | ALL |
| 0714 | 22 | GA | | | 6-8 | 24-51-72 | D04010P | | 14 | | D00544 | D2 | | | ALL |
| 0715 | 22 | GA | | | 4-1 | 24-51-72 | D04010P | | 10 | | D40296J | 11 | | | ALL |
| 0716 | 22 | GA | | | 4-8 | 24-51-72 | D04010P | | 15 | | GD00528 | DC.. | 2 | | 001-099 |
| 0716 | 22 | GA | | | 4-8 | 24-51-72 | GD00528 | | DC.. | 2 | D04010P | 15 | | | 115-199 |
| 0717 | 24 | GK | | | 5-3 | 24-51-72 | D04010P | | 5 | | D04118P | 14 | | | ALL |
| 0718 | 24 | GK | | | 4-11 | 24-51-72 | D04010P | | 1 | | TB0024Z | 5 | BJ | | ALL |
| 0719 | 22 | GA | | | 4-10 | 24-51-72 | D00548 | | D1 | | TB0024Z | 5 | BJ | | ALL |
| 0720 | 22 | GA | | | 5-2 | 24-51-72 | D04118P | | 1 | | TB0024Z | 5 | BJ | | ALL |
| 2001B | 22 | GB | AA | | 2-6 | 24-34-11 | D40246J | | 28 | | D40282J | 11 | | | ALL |
| 2001R | 22 | GB | AA | | 0-0 | 24-34-11 | D40246J | | 27 | | D40282J | 10 | | | ALL |
| 4004B | 24 | GN | AC | | 3-6 | 24-23-11 | D40286J | | 3 | | D02226 | 3 | | | ALL |
| 4004G | 24 | GN | AC | | 0-0 | 24-23-11 | D40286J | | 4 | | D02226 | 4 | | | ALL |
| 4004R | 24 | GN | AC | | 0-0 | 24-23-11 | D40286J | | 1 | | D02226 | 1 | | | ALL |
| 4004Y | 24 | GN | AC | | 0-0 | 24-23-11 | D40286J | | 2 | | D02226 | 2 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0070

Page 5 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0101 | 286N0101 | | | P1-3 MODULE | | | | | | | | | | | |
| 0001 | 22 | | 1E | | 3-0 | 26-11-11 | M00779 | A2 | 1A | | TB0064Y | A012 | BJ | | ALL |
| 0002 | 24 | | 1E | | 4-0 | 34-12-12 | M00779 | F5 | 1A | | D40209J | 5 | | | 001-099 |
| 0002 | 24 | | 1E | | 3-0 | 34-12-12 | M00779 | F5 | 1A | | D40209J | 5 | | | 115-199 |
| 0003 | 22 | | 1E | | 3-0 | 26-11-11 | M00779 | A5 | 1A | | TB0064Y | A012 | BJ | | ALL |
| 0004 | 22 | | 1E | | 2-0 | 26-11-11 | TB0064Y | A012 | BJ | | D40209J | 3 | | | ALL |
| 0005 | 24 | | 1E | | 4-0 | 34-12-22 | M00779 | F2 | 1A | | D40427J | 5 | | | 001-099 |
| 0005 | 24 | | 1E | | 3-0 | 34-12-22 | M00779 | F2 | 1A | | D40427J | 5 | | | 115-199 |
| 0006 | 22 | | 1E | | 3-0 | 34-46-11 | D40427J | 16 | | | L00649 | 2 | BJ | | 001-099 |
| 0006 | 22 | | 1E | | 3-0 | 34-46-11 | D40427J | 16 | | | L00649 | 2 | | | 115-199 |
| 0008 | 22 | | 1E | | 3-0 | 34-46-11 | M00779 | C5 | 1A | | TB0064Y | C011 | BJ | | ALL |
| 0009 | 22 | | 1E | | 2-0 | 32-42-12 | D40427J | 9 | | | TB0064Y | A006 | BJ | | ALL |
| 0011 | 22 | | 1E | | 2-0 | 34-46-11 | TB0064Y | C011 | BJ | | D40209J | 11 | | | ALL |
| 0012 | 22 | | 1E | | 3-0 | 34-46-11 | M00779 | C2 | 1A | | TB0064Y | C011 | BJ | | ALL |
| 0013 | 22 | | 1E | | 3-0 | 34-32-11 | L00237 | 2 | 1A | | D40209J | 13 | | | ALL |
| 0014 | 22 | | 1E | | 3-0 | 34-32-11 | L00238 | 2 | 1A | | D40209J | 14 | | | ALL |
| 0015 | 22 | | 1E | | 3-0 | 34-32-11 | L00239 | 2 | 1A | | D40209J | 15 | | | ALL |
| 0016 | 22 | | 1E | | 3-0 | 34-46-11 | N10015 | 16 | 1A | | TB0064Y | A011 | BJ | | ALL |
| 0019 | 24 | | 1E | | 3-0 | 34-46-11 | N10015 | 2 | 1A | | D40427J | 19 | | | ALL |
| 0022 | 22 | | 1E | | 2-0 | 34-46-11 | TB0064Y | A011 | BJ | | D40427J | 22 | | | ALL |
| 0023 | 22 | | 1E | | 2-0 | 33-16-51 | L00237 | 1 | 1A | | TB0064Z | 17 | BJ | | 001-099 |
| 0023 | 22 | | 1E | | 3-0 | 33-16-51 | L00237 | 1 | 1A | | TB0064Z | 17 | BJ | | 115-199 |
| 0024 | 22 | | 1E | | 2-0 | 33-16-51 | L00237 | 3 | 1A | | TB0064Z | 18 | BJ | | 001-099 |
| 0024 | 22 | | 1E | | 3-0 | 33-16-51 | L00237 | 3 | 1A | | TB0064Z | 18 | BJ | | 115-199 |
| 0025 | 22 | | 1E | | 2-0 | 33-16-51 | L00238 | 1 | 1A | | TB0064Z | 17 | BJ | | 001-099 |
| 0025 | 22 | | 1E | | 3-0 | 33-16-51 | L00238 | 1 | 1A | | TB0064Z | 17 | BJ | | 115-199 |
| 0026 | 22 | | 1E | | 2-0 | 33-16-51 | L00238 | 3 | 1A | | TB0064Z | 18 | BJ | | 001-099 |
| 0026 | 22 | | 1E | | 3-0 | 33-16-51 | L00238 | 3 | 1A | | TB0064Z | 18 | BJ | | 115-199 |
| 0027 | 22 | | 1E | | 2-0 | 33-16-51 | L00239 | 1 | 1A | | TB0064Z | 17 | BJ | | 001-099 |
| 0027 | 22 | | 1E | | 3-0 | 33-16-51 | L00239 | 1 | 1A | | TB0064Z | 17 | BJ | | 115-199 |
| 0028 | 22 | | 1E | | 2-0 | 33-16-51 | L00239 | 3 | 1A | | TB0064Z | 18 | BJ | | 001-099 |
| 0028 | 22 | | 1E | | 3-0 | 33-16-51 | L00239 | 3 | 1A | | TB0064Z | 18 | BJ | | 115-199 |
| 0031 | 22 | | 1E | | 3-0 | 34-46-11 | N10015 | 15 | 1A | | TB0064Y | A011 | BJ | | ALL |
| 0032 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | F3 | 1A | | TB0064Z | 1 | BJ | | ALL |
| 0033 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | F1 | 1A | | TB0064Z | 2 | BJ | | ALL |
| 0034 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | D3 | 1A | | TB0064Z | 1 | BJ | | ALL |
| 0035 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | D1 | 1A | | TB0064Z | 2 | BJ | | ALL |
| 0036 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | A3 | 1A | | TB0064Z | 1 | BJ | | ALL |
| 0037 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | A1 | 1A | | TB0064Z | 2 | BJ | | ALL |
| 0038 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | B3 | 1A | | TB0064Z | 1 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0100

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0101 | 286N0101 | | | | P1-3 MODULE (continued) | | | | | | | | | | | |
| 0039 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | B1 | 1A | | TB0064Z | 2 | BJ | | ALL | |
| 0040 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | E3 | 1A | | TB0064Z | 1 | BJ | | ALL | |
| 0041 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | E1 | 1A | | TB0064Z | 2 | BJ | | ALL | |
| 0042 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | C3 | 1A | | TB0064Z | 1 | BJ | | ALL | |
| 0043 | 22 | | 1E | | 3-0 | 33-16-51 | M00779 | C1 | 1A | | TB0064Z | 2 | BJ | | ALL | |
| 0044 | 22 | | 1E | | 2-0 | 33-16-51 | TB0064Z | 1 | BJ | | D40677J | 1 | | | ALL | |
| 0045 | 22 | | 1E | | 2-0 | 33-16-51 | TB0064Z | 2 | BJ | | D40677J | 2 | | | ALL | |
| 0046 | 22 | | 1E | | 3-0 | 33-16-51 | TS0281 | B3 | 1A | | D40677J | 3 | | | ALL | |
| 0047 | 22 | | 1E | | 3-0 | 33-16-51 | TS0281 | B1 | 1A | | D40677J | 4 | | | ALL | |
| 0048 | 22 | | 1E | | 3-0 | 33-16-51 | TS0281 | B2 | 1A | | D40677J | 5 | | | ALL | |
| 0049 | 22 | | 1E | | 3-0 | 33-16-11 | N10015 | 17 | 1A | | TB0064Z | 4 | BJ | | ALL | |
| 0050 | 22 | | 1E | | 3-0 | 33-16-11 | N10015 | 14 | 1A | | TB0064Z | 4 | BJ | | ALL | |
| 0051 | 22 | | 1E | | 3-0 | 33-16-41 | M00779 | F6 | 1A | | TB0064Z | 15 | BJ | | ALL | |
| 0052 | 22 | | 1E | | 3-0 | 33-16-41 | M00779 | D6 | 1A | | TB0064Z | 15 | BJ | | ALL | |
| 0053 | 22 | | 1E | | 3-0 | 33-16-41 | M00779 | B6 | 1A | | TB0064Z | 15 | BJ | | ALL | |
| 0054 | 22 | | 1E | | 3-0 | 33-16-11 | M00779 | E6 | 1A | | TB0064Z | 4 | BJ | | ALL | |
| 0055 | 22 | | 1E | | 3-0 | 33-16-11 | M00779 | C6 | 1A | | TB0064Z | 4 | BJ | | ALL | |
| 0056 | 22 | | 1E | | 3-0 | 33-16-41 | M00779 | A6 | 1A | | TB0064Z | 15 | BJ | | ALL | |
| 0057 | 22 | | 1E | | 3-0 | 33-16-11 | D40209J | 10 | | | TS0281 | A2 | 1A | | 001-099 | |
| 0057 | 22 | | 1E | | 4-0 | 33-16-11 | D40209J | 10 | | | TS0281 | A2 | 1A | | 115-199 | |
| 0058 | 22 | | 1E | | 3-0 | 33-16-11 | D40209J | 12 | | | TS0281 | A3 | 1A | | 001-099 | |
| 0058 | 22 | | 1E | | 4-0 | 33-16-11 | D40209J | 12 | | | TS0281 | A3 | 1A | | 115-199 | |
| 0059 | 22 | | 1E | | 3-0 | 33-16-11 | D40209J | 16 | | | TS0281 | A1 | 1A | | 001-099 | |
| 0059 | 22 | | 1E | | 4-0 | 33-16-11 | D40209J | 16 | | | TS0281 | A1 | 1A | | 115-199 | |
| 0060 | 22 | | 1E | | 3-0 | 33-16-41 | L00485 | 3 | 1A | | TB0064Z | 15 | BJ | | ALL | |
| 0061 | 22 | | 1E | | 2-0 | 33-16-11 | D40209J | 17 | | | TB0064Z | 4 | BJ | | ALL | |
| 0062 | 22 | | 1E | | 1-0 | 33-16-11 | TB0064Z | 4 | BJ | | TB0064Z | 3 | BJ | | 115-199 | |
| 0064 | 22 | | 1E | | 2-0 | 33-16-21 | D40209J | 20 | | | TB0064Z | 8 | BJ | | ALL | |
| 0065 | 22 | | 1E | | 3-0 | 33-16-21 | TB0064Z | 7 | BJ | | N10015 | 18 | 1A | | ALL | |
| 0066 | 22 | | 1E | | 3-0 | 33-16-21 | TB0064Z | 7 | BJ | | N10015 | 13 | 1A | | ALL | |
| 0067 | 22 | | 1E | | 1-0 | 33-16-21 | TB0064Z | 7 | BJ | | TB0064Z | 8 | BJ | | ALL | |
| 0068 | 22 | | 1E | | 3-0 | 33-16-41 | L00485 | 1 | 1A | | TB0064Z | 10 | BJ | | ALL | |
| 0069 | 22 | | 1E | | 3-0 | 33-16-21 | M00779 | E4 | 1A | | TB0064Z | 8 | BJ | | ALL | |
| 0070 | 22 | | 1E | | 3-0 | 33-16-41 | M00779 | B4 | 1A | | TB0064Z | 10 | BJ | | ALL | |
| 0071 | 22 | | 1E | | 3-0 | 33-16-41 | M00779 | D4 | 1A | | TB0064Z | 10 | BJ | | ALL | |
| 0072 | 22 | | 1E | | 3-0 | 33-16-41 | M00779 | F4 | 1A | | TB0064Z | 10 | BJ | | ALL | |
| 0073 | 22 | | 1E | | 3-0 | 33-16-21 | M00779 | C4 | 1A | | TB0064Z | 8 | BJ | | ALL | |
| 0074 | 22 | | 1E | | 3-0 | 33-16-41 | M00779 | A4 | 1A | | TB0064Z | 10 | BJ | | ALL | |
| 0075 | 22 | | 1E | | 4-0 | 31-41-19 | S10170 | C | \$ | | D40209J | 22 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W0100

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0101 | 286N0101 | | | | P1-3 MODULE (continued) | | | | | | | | | | | |
| 0076 | 22 | | 1E | | 4-0 | 31-41-19 | | S10230 | | C | \$ | D40209J | 23 | | | ALL |
| 0077 | 24 | | 1E | | 4-0 | 31-41-19 | | S10230 | | NO | \$ | D40209J | 24 | | | ALL |
| 0078 | 24 | | 1E | | 4-0 | 31-41-19 | | S10170 | | NO | \$ | D40209J | 25 | | | ALL |
| 0079 | 22 | | 1E | | 3-0 | 33-16-41 | | L00024 | | 1 | 1A | TB0064Z | 9 | BJ | | ALL |
| 0080 | 22 | | 1E | | 3-0 | 33-16-41 | | L00471 | | 1 | 1A | TB0064Z | 9 | BJ | | ALL |
| 0081 | 22 | | 1E | | 3-0 | 33-16-41 | | L00269 | | 1 | 1A | TB0064Z | 9 | BJ | | ALL |
| 0082 | 22 | | 1E | | 1-0 | 33-16-41 | | TB0064Z | | 10 | BJ | TB0064Z | 9 | BJ | | ALL |
| 0083 | 22 | | 1E | | 3-0 | 33-16-41 | | L00471 | | 3 | 1A | TB0064Z | 16 | BJ | | ALL |
| 0084 | 22 | | 1E | | 3-0 | 33-16-41 | | L00269 | | 3 | 1A | TB0064Z | 16 | BJ | | ALL |
| 0085 | 22 | | 1E | | 3-0 | 33-16-41 | | TB0064Z | | 16 | BJ | L00486 | 3 | 1A | | ALL |
| 0086 | 22 | | 1E | | 3-0 | 33-16-41 | | L00024 | | 3 | 1A | TB0064Z | 16 | BJ | | ALL |
| 0087 | 22 | | 1E | | 1-0 | 33-16-41 | | TB0064Z | | 16 | BJ | TB0064Z | 15 | BJ | | ALL |
| 0088 | 22 | | 1E | | 3-0 | 33-16-41 | | TB0064Z | | 9 | BJ | L00486 | 1 | 1A | | ALL |
| 0089 | 20 | | 1E | | 3-0 | 33-13-12 | | L00372 | | =P | B | D40427J | 7 | | | ALL |
| 0090 | 20 | | 1E | | 3-0 | 33-13-12 | | L00372 | | =G | G | D40427J | 8 | | | ALL |
| 0091 | 20 | | 1E | | 3-0 | 33-13-12 | | SM00001 | | | W | D40209J | 29 | | | ALL |
| 0092 | 20 | | 1E | | 3-0 | 33-13-12 | | SM00002 | | | W | D40209J | 30 | | | ALL |
| 0093 | 22 | | 1E | | 4-0 | 31-51-42 | | M00779 | | B2 | 1A | D40209J | 1 | | | 001-099 |
| 0093 | 22 | | 1E | | 3-0 | 31-51-42 | | M00779 | | B2 | 1A | D40209J | 1 | | | 115-199 |
| 0094 | 22 | | 1E | | 4-0 | 31-51-42 | | M00779 | | B5 | 1A | D40209J | 2 | | | 001-099 |
| 0094 | 22 | | 1E | | 3-0 | 31-51-42 | | M00779 | | B5 | 1A | D40209J | 2 | | | 115-199 |
| 0095 | 20 | | 1E | | 3-0 | 33-13-12 | | GD01592 | | ST.. | E | D40427J | 24 | | | 001-099 |
| 0095 | 20 | | 1E | | 4-0 | 33-13-12 | | GD01592 | | ST.. | E | D40427J | 24 | | | 115-199 |
| 0096 | 22 | | 1E | | 3-0 | 32-42-12 | | L00024 | | 2 | 1A | M01174 | A | C | | ALL |
| 0097 | 22 | | 1E | | 2-0 | 32-42-12 | | D40427J | | 11 | | TB0064Y | A006 | BJ | | ALL |
| 0098 | 22 | | 1E | | 3-0 | 32-42-12 | | M01174 | | B | C | TB0064Y | A006 | BJ | | ALL |
| 0101 | 22 | | 1E | | 4-0 | 22-14-11 | | M00779 | | D5 | 1A | D40427J | 13 | | | 001-099 |
| 0101 | 22 | | 1E | | 3-0 | 22-14-11 | | M00779 | | D5 | 1A | D40427J | 13 | | | 115-199 |
| 0102 | 22 | | 1E | | 3-0 | 22-14-11 | | L00269 | | 2 | 1A | D40427J | 12 | | | ALL |
| 0103 | 22 | | 1E | | 3-0 | 22-34-11 | | L00486 | | 2 | 1A | D40427J | 6 | | | ALL |
| 0106 | 22 | | 1E | | 3-0 | 33-16-61 | | L00475 | | 1 | 1A | D40677J | 7 | | | ALL |
| 0107 | 22 | | 1E | | 3-0 | 33-16-51 | | L00475 | | 3 | 1A | TB0064Z | 18 | BJ | | ALL |
| 0108 | 24 | | 1E | | 3-0 | 34-46-11 | | N10015 | | 3 | 1A | D40427J | 20 | | | ALL |
| 0109 | 22 | | 1E | | 3-0 | 33-16-51 | | L00474 | | 1 | 1A | TB0064Y | C013 | BJ | | ALL |
| 0110 | 22 | | 1E | | 3-0 | 33-16-51 | | L00474 | | 3 | 1A | TB0064Y | A013 | BJ | | ALL |
| 0111 | 24 | | 1E | | 3-0 | 34-61-15 | | L00471 | | 2 | 1A | D40427J | 3 | | | ALL |
| 0112 | 24 | | 1E | | 3-0 | 34-16-11 | | L00485 | | 2 | 1A | D40427J | 4 | | | ALL |
| 0113 | 22 | | 1E | | 2-0 | 33-16-41 | | TB0064Z | | 15 | BJ | D40427J | 1 | | | ALL |
| 0114 | 22 | | 1E | | 2-0 | 33-16-41 | | TB0064Z | | 10 | BJ | D40427J | 2 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0100

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------|-------------|----|-------|-----|-------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0101 | 286N0101 | | | | P1-3 MODULE (continued) | | | | | | | | | | | |
| 0115 | 22 | | 1E | | 3-0 | 79-33-11 | L00474 | 2 | 1A | | | D40209J | 19 | | | ALL |
| 0116 | 22 | | 1E | | 3-0 | 79-33-11 | L00475 | 2 | 1A | | | D40427J | 10 | | | ALL |
| 0119 | 24 | | 1E | | 3-0 | 21-33-12 | M00779 | E2 | 1A | | | TB0064Y | C005 | BJ | | ALL |
| 0120 | 24 | | 1E | | 3-0 | 21-33-12 | M00779 | E5 | 1A | | | TB0064Y | C005 | BJ | | ALL |
| 0121 | 24 | | 1E | | 2-0 | 21-33-12 | TB0064Y | C005 | BJ | | | D40209J | 4 | | | ALL |
| 0122 | 20 | | 1E | | 3-0 | 33-13-12 | L00542 | =P | B | | | SM00001 | | W | | ALL |
| 0123 | 20 | | 1E | | 3-0 | 33-13-12 | L00542 | =G | G | | | SM00002 | | W | | ALL |
| 0124 | 20 | | 1E | | 2-0 | 33-13-12 | L00371 | =P | B | | | SM00001 | | W | | 001-099 |
| 0124 | 20 | | 1E | | 1-0 | 33-13-12 | L00371 | =P | B | | | SM00001 | | W | | 115-199 |
| 0125 | 20 | | 1E | | 2-0 | 33-13-12 | L00371 | =G | G | | | SM00002 | | W | | 001-099 |
| 0125 | 20 | | 1E | | 1-0 | 33-13-12 | L00371 | =G | G | | | SM00002 | | W | | 115-199 |
| 0126 | 20 | | 1E | | 3-0 | 33-13-12 | S10390 | 13 | 1A | | | SM00001 | | W | | ALL |
| 0128 | 20 | | 1E | | 3-0 | 33-13-12 | S10390 | 15 | 1A | | | SM00002 | | W | | ALL |
| 0131 | 22 | | 1E | | 3-0 | 29-21-32 | S10390 | 9 | 1A | | | D40427J | 23 | | | ALL |
| 0133 | 22 | | 1E | | 3-0 | 33-16-51 | L00491 | 1 | 1A | | | TB0064Y | C013 | BJ | | 001-099 |
| 0133 | 22 | | 1E | | 2-0 | 33-16-51 | L00491 | 1 | 1A | | | TB0064Y | C013 | BJ | | 115-199 |
| 0134 | 24 | | 1E | | 3-0 | 32-41-11 | L00491 | 2 | 1A | | | D40677J | 9 | | | ALL |
| 0135 | 22 | | 1E | | 3-0 | 33-16-51 | L00491 | 3 | 1A | | | TB0064Y | A013 | BJ | | 001-099 |
| 0135 | 22 | | 1E | | 2-0 | 33-16-51 | L00491 | 3 | 1A | | | TB0064Y | A013 | BJ | | 115-199 |
| 0136 | 22 | | 1E | | 3-0 | 33-16-51 | TB0064Z | 17 | BJ | | | L00649 | 1 | 1A | | ALL |
| 0137 | 22 | | 1E | | 3-0 | 33-16-51 | TB0064Z | 18 | BJ | | | L00649 | 3 | 1A | | ALL |
| 0138 | 22 | | 1E | | 3-0 | 29-21-32 | S10390 | 5 | 1A | | | D40427J | 18 | | | ALL |
| 0139 | 22 | | 1E | | 3-0 | 29-21-32 | S10390 | 7 | 1A | | | D40209J | 27 | | | ALL |
| 0140 | 22 | | 1E | | 3-0 | 29-21-32 | S10390 | 8 | 1A | | | D40209J | 28 | | | ALL |
| 0141 | 22 | | 1E | | 1-0 | 33-16-51 | TB0064Z | 17 | BJ | | | TB0064Z | 2 | BJ | | ALL |
| 0142 | 22 | | 1E | | 1-0 | 33-16-51 | TB0064Z | 18 | BJ | | | TB0064Z | 1 | BJ | | ALL |
| 0151 | 22 | | 1E | | 2-0 | 33-16-51 | D40677J | 8 | | | | TB0064Y | C013 | BJ | | ALL |
| 0152 | 22 | | 1E | | 2-0 | 33-16-51 | D40677J | 10 | | | | TB0064Y | A013 | BJ | | ALL |
| 0153 | 24 | | 1E | | 3-0 | 31-51-43 | L00716 | 2 | 1A | | | D40209J | 34 | | | ALL |
| 0154 | 22 | | 1E | | 3-0 | 33-16-41 | L00716 | 3 | 1A | | | TB0064Z | 16 | BJ | | ALL |
| 0155 | 22 | | 1E | | 3-0 | 33-16-41 | L00716 | 1 | 1A | | | TB0064Z | 9 | BJ | | ALL |
| 0156 | 22 | | 1E | | 2-0 | 32-42-12 | D40427J | 14 | | | | TB0064Y | A006 | BJ | | 001-099 |
| 0156 | 22 | | 6A | | 2-0 | 32-42-12 | D40427J | 14 | | | | TB0064Y | A006 | BJ | | 115-199 |
| 1002 | 20 | | EE | AB | 3-0 | 29-21-32 | S10390 | 6 | 1A | | | D40427J | 17 | | | ALL |
| 1002Z | | | | AB | 0-0 | 29-21-32 | S10390 | DED | | | | D40427J | DED | | | ALL |
| 1003 | 22 | | CN | AC | 4-0 | 22-14-11 | M00779 | D2 | 1A | | | D40209J | 26 | | | 001-099 |
| 1003 | 22 | | CN | AC | 3-0 | 22-14-11 | M00779 | D2 | 1A | | | D40209J | 26 | | | 115-199 |
| 1003Z | | | | AC | 0-0 | 22-14-11 | M00779 | DED | | | | D40209J | DED | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0100

Page 4 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0110 | 286N0110 | | | P11-1 MODULE WIRING - LEFT - STBY - BUSSES | | | | | | | | | | | |
| 0001 | 16 | | GA | | 6-0 | 24-51-12 | TB5001 | 2 | E | | C00513 | =B | D | | 001-099 |
| 0001 | 16 | | GA | | 6-0 | 24-51-12 | TB5001 | 2 | E | | C01025 | =B | D | * | 115-199 |
| 0002 | 16 | | GA | | 7-0 | 24-51-12 | TB5001 | 3 | E | | C00592 | =B | D | | ALL |
| 0003 | 16 | | GA | | 7-0 | 24-51-12 | TB5001 | 4 | E | | C00615 | =B | D | | ALL |
| 0005 | 16 | | GA | | 2-0 | 24-51-12 | C01536 | =B | D | | C01025 | =B | D | | 001-099 |
| 0005 | 16 | | GA | | 2-0 | 24-51-12 | C01536 | =B | D | | C01025 | =B | D | * | 115-199 |
| 0010 | 16 | | GA | | 3-0 | 24-51-72 | C00586 | =B | D | | C00639 | =B | D | * | ALL |
| 0016 | 08 | | HA | | 4-5 | 24-54-11 | TB5001 | 1 | E | | C04035 | =B | D | | 001-099 |
| 0016 | 08 | | HA | | 3-8 | 24-54-11 | TB5001 | 1 | E | | C04035 | =B | D | | 115-199 |
| 0017 | 12 | | HA | | 1-1 | 24-54-11 | C01539 | =B | D | | C00525 | =B | D | | 001-099 |
| 0017 | 12 | | HA | | 1-2 | 24-54-11 | C01539 | =B | D | | C00525 | =B | D | | 115-199 |
| 0018 | 12 | | HA | | 2-7 | 24-54-11 | C01023 | =B | D | | C00539 | =B | D | | 001-004 |
| 0018 | 12 | | HA | | 2-0 | 24-54-11 | C01023 | =B | D | | C00539 | =B | D | | 005-099 |
| 0018 | 12 | | HA | | 2-9 | 24-54-11 | C01023 | =B | D | | C00539 | =B | D | | 115-199 |
| 0019 | 16 | | GA | | 3-0 | 24-54-73 | C01521 | =B | D | * | C00607 | =B | D | | 001-002 |
| 0026 | 14 | | GA | | 6-0 | 24-53-11 | TB5001 | 5 | E | | C01037 | =B | D | | 001-099 |
| 0026 | 14 | | GA | | 7-0 | 24-53-11 | TB5001 | 5 | E | | C01037 | =B | D | | 115-199 |
| 0029 | 16 | | GA | | 9-0 | 24-51-72 | TB5003 | 8 | E | | C00584 | =B | D | | 001-099 |
| 0029 | 16 | | GA | | 10-0 | 24-51-72 | TB5003 | 8 | E | | C00584 | =B | D | | 115-199 |
| 0030 | 16 | | GA | | 8-0 | 24-51-72 | TB5003 | 9 | E | | C00637 | =B | D | * | 001-099 |
| 0030 | 16 | | GA | | 9-0 | 24-51-72 | TB5003 | 9 | E | | C00637 | =B | D | * | 115-199 |
| 0031 | 16 | | GA | | 8-0 | 24-51-72 | TB5003 | 10 | E | | C00639 | =B | D | * | 001-099 |
| 0031 | 16 | | GA | | 9-0 | 24-51-72 | TB5003 | 10 | E | | C00639 | =B | D | * | 115-199 |
| 0034 | 16 | | GA | | 3-0 | 24-51-72 | C00588 | =B | D | | C00600 | =B | D | | 001-099 |
| 0034 | 16 | | GA | | 4-0 | 24-51-72 | C00588 | =B | D | | C00600 | =B | D | | 115-199 |
| 0035 | 16 | | GA | | 3-0 | 24-51-12 | C00501 | =B | D | | C00607 | =B | D | | 003-099 |
| 0035 | 16 | | GA | | 4-0 | 24-51-12 | C00501 | =B | D | | C00607 | =B | D | | 115-199 |
| 0038 | 12 | | HA | | 1-2 | 24-54-11 | C00512 | =B | D | | C00641 | =B | D | | 001-099 |
| 0041 | 16 | | GA | | 3-0 | 24-51-72 | C00637 | =B | D | * | C00603 | =B | D | | 001-099 |
| 0041 | 16 | | GA | | 3-0 | 24-51-72 | C00637 | =B | D | * | C04600 | =B | D | | 115-199 |
| 0042 | 12 | | HA | | 2-3 | 24-51-15 | C00582 | =B | D | * | C03005 | B2 | D | * | 001-099 |
| 0042 | 12 | | HA | | 2-8 | 24-51-15 | C03005 | B2 | D | * | C00582 | =B | D | * | 115-199 |
| 0043 | 12 | | HA | | 2-9 | 24-51-15 | C00582 | =B | D | * | C00611 | =B | D | * | 001-099 |
| 0043 | 12 | | HA | | 3-2 | 24-51-15 | C00582 | =B | D | * | C00611 | =B | D | * | 115-199 |
| 0044 | 18 | | GA | | 7-0 | 24-51-15 | C01008 | =B | D | | TB5001 | 12 | E | | 001-099 |
| 0044 | 18 | | GA | | 6-0 | 24-51-15 | C01008 | =B | D | | TB5001 | 12 | E | | 115-199 |
| 0048 | 12 | | HA | | 1-4 | 24-51-15 | C00611 | =B | D | * | C04051 | =B | D | | 001-099 |
| 0048 | 12 | | HA | | 1-5 | 24-51-15 | C00611 | =B | D | * | C04051 | =B | D | | 115-199 |
| 0050 | 16 | | GA | | 3-0 | 24-54-73 | C00567 | =B | D | | C01031 | =B | D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|--------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0110 | | 286N0110 | | | | P11-1 MODULE WIRING - LEFT - STBY - BUSSES (continued) | | | | | | | | | |
| 0052 | 16 | GA | | | 3-0 | 24-54-73 | C01017 | =B | D | | C01541 | =B | D | | ALL |
| 0071 | 12 | HA | | | 4-0 | 24-54-11 | C04509 | =B | D | | C00546 | =B | D | | 002 |
| 0300 | 12 | HA | | | 6-1 | 24-51-15 | C03005 | A2 | D | | TB5001 | 9 | E | | ALL |
| 0301 | 12 | HA | | | 6-1 | 24-51-15 | C03005 | B2 | D | * | TB5001 | 10 | E | | ALL |
| 0302 | 12 | HA | | | 6-1 | 24-51-15 | C03005 | C2 | D | | TB5001 | 11 | E | | ALL |
| 0701 | 12 | HA | | | 6-1 | 24-54-73 | TB5005 | 1 | E | | C00826 | =B | D | | 001-099 |
| 0714 | 16 | GA | | | 7-0 | 24-54-73 | TB5005 | 2 | E | | C01437 | =B | D | | 001-099 |
| 0727 | 12 | HA | | | 1-10 | 24-54-73 | C00604 | =B | D | | C01560 | =B | D | | 001-099 |
| 0730 | 16 | GA | | | 2-0 | 24-54-73 | C04205 | =B | D | | C00566 | =B | D | | 001-099 |
| 0738 | 16 | GA | | | 3-0 | 24-54-73 | C01521 | =B | D | * | C01438 | =B | D | | 001-002 |
| 0738 | 16 | GA | | | 3-0 | 24-54-73 | C01521 | =B | D | | C01438 | =B | D | | 003-099 |
| ZZAA | 02 | ZB | | | 0-0 | 24-51-72 | C00639 | =B | D | | C04263 | =B | D | | 001, 003-099 |
| ZZAA | 02 | ZB | | | 0-0 | 24-51-72 | C04263 | =B | D | | C00639 | =B | D | | 115-199 |
| ZZAB | 02 | ZB | | | 0-0 | 24-51-15 | C00609 | =B | D | | C00597 | =B | D | | ALL |
| ZZAC | 00 | ZB | | | 0-0 | 24-54-73 | C00567 | =B | D | | C00573 | =B | D | | 001-099 |
| ZZAD | 00 | ZB | | | 0-0 | 24-54-73 | C00604 | =B | D | | C00591 | =B | D | | 001-099 |
| ZZAF | 02 | ZB | | | 0-0 | 24-54-11 | C04035 | =B | D | | C04033 | =B | D | | ALL |
| ZZAH | 02 | ZB | | | 0-0 | 24-54-11 | C00525 | =B | D | | C00512 | =B | D | | ALL |
| ZZAJ | 00 | ZB | | | 0-0 | 24-54-73 | C00622 | =B | D | | C00591 | =B | D | | 001-099 |
| ZZAK | 02 | ZB | | | 0-0 | 24-51-15 | C01522 | =B | D | | C01008 | =B | D | | ALL |
| ZZAL | 03 | ZB | | | 0-0 | 24-54-73 | C00702 | =B | D | | C04039 | =B | D | | 001-099 |
| ZZAP | 04 | ZB | | | 0-0 | 24-51-72 | C00633 | =B | D | | C00580 | =B | D | | ALL |
| ZZAR | 03 | ZB | | | 0-0 | 24-54-73 | C00826 | =B | D | | C01120 | =B | D | | 001-099 |
| ZZAS | 00 | ZB | | | 0-0 | 24-54-73 | C04118 | =B | D | | C00606 | =B | D | | 001-099 |
| ZZAT | 00 | ZB | | | 0-0 | 24-54-73 | C00606 | =B | D | | C00595 | =B | D | | 001-099 |
| ZZBD | 02 | ZB | | | 0-0 | 24-54-11 | C00539 | =B | D | | C00546 | =B | D | | 001-099 |
| ZZDB | 02 | ZB | | | 0-0 | 24-51-72 | C00586 | =B | D | | C00588 | =B | D | | ALL |
| ZZDC | 02 | ZB | | | 0-0 | 24-54-73 | C04665 | =B | D | | C04664 | =B | D | | 001-099 |
| ZZEE | 00 | ZB | | | 0-0 | 24-51-72 | C00593 | =B | D | | C00633 | =B | D | | 001-099 |
| ZZEE | 00 | ZB | | | 0-0 | 24-51-72 | C00633 | =B | D | | C00593 | =B | D | | 115-199 |
| ZZEF | 00 | ZB | | | 0-0 | 24-51-72 | C00580 | =B | D | | C00584 | =B | D | | 115-199 |
| ZZFF | 00 | ZB | | | 0-0 | 24-51-72 | C00593 | =B | D | | C00584 | =B | D | | 115-199 |
| ZZHV | 02 | ZB | | | 0-0 | 24-53-11 | C01523 | =B | D | | C01037 | =B | D | | ALL |
| ZZJB | 05 | ZB | | | 0-0 | 24-54-73 | C01533 | =B | D | | C01529 | =B | D | | 001-099 |
| ZZJC | 03 | ZB | | | 0-0 | 24-54-73 | C00622 | =B | D | | C00604 | =B | D | | 001-099 |
| ZZJD | 02 | ZB | | | 0-0 | 24-54-73 | C00521 | =B | D | | C01560 | =B | D | | 001-099 |
| ZZKA | 04 | ZB | | | 0-0 | 24-54-73 | C01434 | =B | D | | C01438 | =B | D | | 001-099 |
| ZZKC | 02 | ZB | | | 0-0 | 24-54-73 | C01283 | =B | D | | C01246 | =B | D | | 001-099 |
| ZZKD | 02 | ZB | | | 0-0 | 24-54-73 | C04206 | =B | D | | C04205 | =B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0110 | 286N0110 | | | P11-1 MODULE WIRING - LEFT - STBY - BUSSES (continued) | | | | | | | | | | | |
| ZZKE | 03 | | ZB | | 0-0 | 24-54-73 | C00595 | =B | D | | C04118 | =B | D | | 001-099 |
| ZZLE | 04 | | ZB | | 0-0 | 24-54-73 | C00573 | =B | D | | C00683 | =B | D | | 001-099 |
| ZZOA | 00 | | ZB | | 0-0 | 24-54-73 | C00653 | =B | D | | C04039 | =B | D | | 001-099 |
| ZZOB | 00 | | ZB | | 0-0 | 24-54-73 | C00702 | =B | D | | C00653 | =B | D | | 001-099 |
| ZZOD | 00 | | ZB | | 0-0 | 24-51-72 | C00584 | =B | D | | C00593 | =B | D | | 001-099 |
| ZZOE | 00 | | ZB | | 0-0 | 24-51-72 | C00584 | =B | D | | C00580 | =B | D | | 001-099 |
| ZZOF | 00 | | ZB | | 0-0 | 24-54-73 | C00826 | =B | D | | C04194 | =B | D | | 001-099 |
| ZZOG | 00 | | ZB | | 0-0 | 24-54-73 | C04194 | =B | D | | C01120 | =B | D | | 001-099 |
| ZZPA | 02 | | ZB | | 0-0 | 24-54-73 | C01480 | =B | D | | C01482 | =B | D | | 001-099 |
| ZZPD | 00 | | ZB | | 0-0 | 24-54-73 | C01438 | =B | D | | C01437 | =B | D | | 001-099 |
| ZZPE | 00 | | ZB | | 0-0 | 24-54-73 | C01435 | =B | D | | C01437 | =B | D | | 001-099 |
| ZZPF | 00 | | ZB | | 0-0 | 24-54-73 | C01435 | =B | D | | C01434 | =B | D | | 001-099 |
| ZZPG | 00 | | ZB | | 0-0 | 24-54-73 | C01529 | =B | D | | C01528 | =B | D | | 001-099 |
| ZZPH | 00 | | ZB | | 0-0 | 24-54-73 | C01039 | =B | D | | C01528 | =B | D | | 001-099 |
| ZZPI | 00 | | ZB | | 0-0 | 24-54-73 | C00567 | =B | D | | C00658 | =B | D | | 001-099 |
| ZZPJ | 00 | | ZB | | 0-0 | 24-54-73 | C00683 | =B | D | | C00658 | =B | D | | 001-099 |
| ZZPK | 00 | | ZB | | 0-0 | 24-54-73 | C01039 | =B | D | | C01033 | =B | D | | 001-099 |
| ZZPL | 00 | | ZB | | 0-0 | 24-54-73 | C01533 | =B | D | | C01033 | =B | D | | 001-099 |
| ZZXA | 02 | | ZA | | 0-0 | 24-51-12 | C01025 | =B | D | | C00501 | =B | D | | ALL |
| ZZXB | 02 | | ZA | | 0-0 | 24-51-12 | C00513 | =B | D | | C00501 | =B | D | | 001-099 |
| ZZXB | 02 | | ZA | | 0-0 | 24-51-12 | C00501 | =B | D | | C00513 | =B | D | | 115-199 |
| ZZXC | 02 | | ZA | | 0-0 | 24-51-15 | C03005 | C2 | D | | C00597 | =B | D | | ALL |
| ZZXE | 02 | | ZA | | 0-0 | 24-51-15 | C03005 | B2 | D | | C00592 | =B | D | | 001-099 |
| ZZXG | 02 | | ZA | | 0-0 | 24-54-73 | C04110 | =B | D | | C00573 | =B | D | | 001-099 |
| ZZXG | 02 | | ZA | | 0-0 | 24-51-12 | C00592 | =B | D | | C04443 | =B | D | | 115-199 |
| ZZXH | 02 | | ZA | | 0-0 | 24-51-12 | C00592 | =B | D | | C04443 | =B | D | | 001-099 |
| ZZXJ | 02 | | ZA | | 0-0 | 24-54-73 | C00725 | =B | D | | C00573 | =B | D | | 115-199 |
| ZZXL | 02 | | ZA | | 0-0 | 24-54-11 | C00522 | =B | D | | C00516 | =B | D | | ALL |
| ZZXR | 02 | | ZA | | 0-0 | 24-54-11 | C01539 | =B | D | | C01023 | =B | D | | ALL |
| ZZXS | 02 | | ZA | | 0-0 | 24-54-11 | C01531 | =B | D | | C00525 | =B | D | | 001-099 |
| ZZXT | 02 | | ZA | | 0-0 | 24-54-11 | C00512 | =B | D | | C00516 | =B | D | | ALL |
| ZZXW | 02 | | ZA | | 0-0 | 24-53-11 | C01523 | =B | D | | C01002 | =B | D | | ALL |
| ZZXZ | 02 | | ZA | | 0-0 | 24-54-11 | C01531 | =B | D | | C04033 | =B | D | | 001-099 |
| ZZYG | 02 | | ZA | | 0-0 | 24-54-73 | C01528 | =B | D | | C01541 | =B | D | | 001-099 |
| ZZYJ | 02 | | ZA | | 0-0 | 24-54-73 | C00683 | =B | D | | C01529 | =B | D | | 001-099 |
| ZZYM | 02 | | ZA | | 0-0 | 24-54-73 | C00619 | =B | D | | C04665 | =B | D | | 001-099 |
| ZZYZ | 02 | | ZA | | 0-0 | 24-54-11 | C01531 | =B | D | | C04033 | =B | D | | 115-199 |
| ZZZA | 02 | | ZA | | 0-0 | 24-54-73 | C01435 | =B | D | | C01537 | =B | D | | 001-099 |
| ZZZB | 02 | | ZA | | 0-0 | 24-54-73 | C01434 | =B | D | | C01538 | =B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------------|---------|-------|------|------|--------|-------|------|------|---------|-------------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0110 | 286N0110 | | | P11-1 MODULE WIRING - LEFT - STBY - BUSSES (continued) | | | | | | | | | | | |
| ZZZC | 02 | | ZA | 0-0 | 24-54-73 | C01538 | =B | D | | C01246 | =B | D | | 001-099 | |
| ZZZD | 02 | | ZA | 0-0 | 24-54-73 | C00544 | =B | D | | C01338 | =B | D | | 001-099 | |
| ZZZE | 02 | | ZA | 0-0 | 24-54-73 | C00606 | =B | D | | C00635 | =B | D | | 001-099 | |
| ZZZF | 02 | | ZA | 0-0 | 24-54-73 | C01283 | =B | D | | C00635 | =B | D | | 001-099 | |
| ZZZG | 02 | | ZA | 0-0 | 24-54-73 | C00521 | =B | D | | C00658 | =B | D | | 001-099 | |
| ZZZH | 02 | | ZA | 0-0 | 24-54-73 | C01537 | =B | D | | C00770 | =B | D | | 001-099 | |
| ZZZI | 02 | | ZA | 0-0 | 24-54-73 | C00625 | =B | D | | C04206 | =B | D | | 001-099 | |
| ZZZJ | 02 | | ZA | 0-0 | 24-54-73 | C00591 | =B | D | | C00619 | =B | D | | 001-099 | |
| ZZZK | 02 | | ZA | 0-0 | 24-54-73 | C01533 | =B | D | | C01534 | =B | D | | 001-099 | |
| ZZZL | 02 | | ZA | 0-0 | 24-54-73 | C00567 | =B | D | | C04039 | =B | D | | 001-099 | |
| ZZZM | 02 | | ZA | 0-0 | 24-54-73 | C01338 | =B | D | | C00619 | =B | D | | 001-099 | |
| ZZZN | 02 | | ZA | 0-0 | 24-54-73 | C01480 | =B | D | | C01039 | =B | D | | 001-099 | |
| ZZZP | 02 | | ZA | 0-0 | 24-54-73 | C01534 | =B | D | | C00826 | =B | D | | 001-099 | |
| ZZZQ | 02 | | ZA | 0-0 | 24-54-73 | C00770 | =B | D | | C04206 | =B | D | | 001-099 | |
| ZZZR | 02 | | ZA | 0-0 | 24-54-73 | C00595 | =B | D | | C01337 | =B | D | | 001-099 | |
| ZZZW | 02 | | ZA | 0-0 | 24-54-11 | C01531 | =B | D | | C00525 | =B | D | | 115-199 | |
| W0112 | 286N0112 | | | P11-3 MODULE WIRING - LEFT BUSES | | | | | | | | | | | |
| 0001 | 08 | | HA | 3-9 | 24-54-11 | TB5003 | 4 | E | | C01171 | =B | D | | 001-099 | |
| 0001 | 08 | | HA | 4-5 | 24-54-11 | TB5003 | 4 | E | | C01171 | =B | D | | 115-199 | |
| 0002 | 08 | | HA | 0-10 | 24-54-11 | C01136 | =B | D | | C00743 | =B | D | | 001-099 | |
| 0002 | 08 | | HA | 0-11 | 24-54-11 | C01136 | =B | D | | C00743 | =B | D | | 115-199 | |
| 0008 | 08 | | HA | 2-9 | 24-54-11 | C01339 | =B | KA | | C00705 | =B | D | | 001-099 | |
| 0008 | 08 | | HA | 2-6 | 24-54-11 | C01339 | =B | KA | * | C00705 | =B | D | | 115-199 | |
| 0009 | 08 | | HA | 0-8 | 24-54-11 | C00660 | =B | D | | C01339 | =B | KA | * | 001-099 | |
| 0009 | 08 | | HA | 1-0 | 24-54-11 | C00660 | =B | D | | C01339 | =B | KA | * | 115-199 | |
| 0010 | 12 | | HA | 1-9 | 24-54-11 | C04024 | =B | D | | C04119 | =B | D | | 001-099 | |
| 0011 | 12 | | HA | 3-8 | 24-54-11 | C00824 | =B | D | | C01297 | =B | D | | 001-099 | |
| 0011 | 08 | | HA | 3-7 | 24-54-11 | C00824 | =B | D | | C01297 | =B | D | | 115-199 | |
| 0013 | 12 | | HA | 2-0 | 24-54-11 | C04069 | =B | D | | C04043 | =B | D | | 001-099 | |
| 0013 | 08 | | HA | 1-1 | 24-54-11 | C04071 | =B | D | | C04043 | =B | D | | 115-199 | |
| 0018 | 08 | | HA | 0-4 | 24-54-11 | C04178 | =B | D | | C04196 | =B | D | | 115-199 | |
| 0019 | 08 | | HA | 1-0 | 24-54-11 | C01182 | =B | D | | C01128 | =B | KA | * | 001-099 | |
| 0019 | 08 | | HA | 0-5 | 24-54-11 | C01181 | =B | D | | C01128 | =B | KA | * | 115-199 | |
| 0020 | 08 | | HA | 2-3 | 24-54-11 | C01128 | =B | KA | * | C01143 | =B | D | | 001-099 | |
| 0020 | 08 | | HA | 0-6 | 24-54-11 | C01128 | =B | KA | * | C01143 | =B | D | | 115-199 | |
| 0022 | 12 | | HA | 6-6 | 24-51-15 | TB5001 | 9 | E | | C01241 | =B | D | | 001-099 | |
| 0022 | 12 | | HA | 6-0 | 24-51-15 | C01241 | =B | D | | TB5001 | 9 | E | | 115-199 | |
| 0023 | 12 | | HA | 5-2 | 24-51-15 | TB5001 | 10 | E | | C04298 | =B | D | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-------------|----|----|---|-------------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0112 | 286N0112 | | | P11-3 MODULE WIRING - LEFT BUSSES (continued) | | | | | | | | | | | |
| 0023 | 12 | | HA | | 5-0 | 24-51-15 | C04298 | =B | D | | TB5001 | 10 | E | | 115-199 |
| 0024 | 12 | | HA | | 5-9 | 24-51-15 | TB5001 | 11 | E | | C04038 | =B | D | | 001-099 |
| 0024 | 12 | | HA | | 5-6 | 24-51-15 | C04038 | =B | D | | TB5001 | 11 | E | | 115-199 |
| 0025 | 12 | | HA | | 1-2 | 24-51-15 | C00673 | =B | D | | C01289 | =B | D | * | 001-099 |
| 0025 | 12 | | HA | | 1-2 | 24-51-15 | C01289 | =B | D | * | C00673 | =B | D | | 115-199 |
| 0026 | 12 | | HA | | 6-2 | 24-51-15 | TB5001 | 12 | E | | C01034 | =B | D | | 001-099 |
| 0026 | 12 | | HA | | 6-0 | 24-51-15 | C01034 | =B | D | | TB5001 | 12 | E | | 115-199 |
| 0027 | 12 | | HA | | 1-6 | 24-51-15 | C01289 | =B | D | * | C00686 | =B | D | | 001-099 |
| 0027 | 12 | | HA | | 1-6 | 24-51-15 | C00686 | =B | D | | C01289 | =B | D | * | 115-199 |
| 0101 | 16 | | GA | | 7-0 | 24-51-11 | TB5003 | 5 | E | | C04280 | =B | D | * | ALL |
| 0102 | 16 | | GA | | 4-0 | 24-51-11 | C04280 | =B | D | * | C01248 | =B | D | * | 001-099 |
| 0108 | 16 | | GA | | 8-0 | 24-51-72 | TB5003 | 9 | E | | C01237 | =B | D | | 001-099 |
| 0108 | 16 | | GA | | 7-0 | 24-51-72 | TB5003 | 9 | E | | C01237 | =B | D | | 115-199 |
| 0111 | 16 | | GA | | 4-0 | 24-51-11 | C01248 | =B | D | * | C04081 | =B | D | | 001-099 |
| 0112 | 16 | | GA | | 5-0 | 24-51-11 | C04078 | =B | D | | C04356 | =B | D | | 001-099 |
| 0201 | 14 | | GA | | 8-0 | 24-53-11 | TB5001 | 5 | E | | C01252 | =B | D | * | ALL |
| 0202 | 14 | | GA | | 3-0 | 24-53-11 | C01252 | =B | D | * | C01498 | =B | D | * | ALL |
| 0203 | 14 | | GA | | 3-0 | 24-53-11 | C01498 | =B | D | * | C04101 | =B | D | | ALL |
| 0204 | 14 | | GA | | 4-0 | 24-53-11 | C01252 | =B | D | | C00564 | =B | D | | 001-099 |
| 0204 | 14 | | GA | | 4-0 | 24-53-11 | C01252 | =B | D | * | C00564 | =B | D | | 115-199 |
| 0205 | 16 | | GA | | 7-0 | 24-51-12 | TB5001 | 4 | E | | C00520 | =B | D | * | 001-099 |
| 0205 | 12 | | HA | | 6-3 | 24-51-12 | TB5001 | 4 | E | | C00520 | =B | D | * | 115-199 |
| 0206 | 16 | | GA | | 5-0 | 24-51-12 | C00520 | =B | D | * | C00561 | =B | D | * | 001-099 |
| 0206 | 12 | | HA | | 4-0 | 24-51-12 | C00520 | =B | D | * | C00561 | =B | D | | 115-199 |
| 0207 | 08 | | HA | | 6-8 | 24-54-11 | TB5001 | 1 | E | | C01290 | =B | D | | 001-099 |
| 0207 | 08 | | HA | | 6-0 | 24-54-11 | TB5001 | 1 | E | | C01290 | =B | D | | 115-199 |
| 0208 | 12 | | HA | | 4-1 | 24-54-11 | C01298 | =B | D | | C00578 | =B | D | * | 001-099 |
| 0208 | 12 | | HA | | 3-11 | 24-54-11 | C01298 | =B | D | | C00578 | =B | D | | 115-199 |
| 0209 | 16 | | GA | | 8-0 | 24-51-12 | TB5001 | 3 | E | | C04283 | =B | D | * | 001-099 |
| 0209 | 16 | | GA | | 5-0 | 24-51-11 | C04078 | =B | D | | C04356 | =B | D | | 115-199 |
| 0210 | 22 | | GA | | 7-0 | 24-51-72 | C04226 | =L | D | | TB5001 | 6 | E | | ALL |
| 0211 | 22 | | GA | | 7-0 | 24-51-72 | C04228 | =L | D | | TB5001 | 7 | E | | ALL |
| 0212 | 22 | | GA | | 7-0 | 24-51-72 | C04230 | =L | D | | TB5001 | 8 | E | | ALL |
| 0213 | 12 | | HA | | 1-6 | 24-54-11 | C01022 | =B | D | | C00578 | =B | D | * | 001-099 |
| 0213 | 12 | | HA | | 2-4 | 24-54-11 | C01412 | =B | D | | C00578 | =B | D | | 115-199 |
| 0214 | 16 | | GA | | 8-0 | 24-51-12 | C04226 | =B | D | | TB5001 | 2 | E | | ALL |
| 0215 | 16 | | GA | | 4-0 | 24-51-12 | C04228 | =B | D | | C04283 | =B | D | * | 001-099 |
| 0215 | 16 | | GA | | 7-0 | 24-51-12 | C04228 | =B | D | * | TB5001 | 3 | E | | 115-199 |
| 0216 | 16 | | GA | | 4-0 | 24-51-12 | C04230 | =B | D | | C00561 | =B | D | * | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0112 | 286N0112 | | | P11-3 MODULE WIRING - LEFT BUSSES (continued) | | | | | | | | | | | |
| 0216 | 16 | | GA | | 7-0 | 24-51-12 | C04230 | =B | D | | TB5001 | 4 | E | | 115-199 |
| 0217 | 16 | | GA | | 4-0 | 24-51-12 | C04228 | =B | D | * | C04283 | =B | D | | 115-199 |
| 0219 | 12 | | HA | | 2-3 | 24-54-11 | C04032 | =B | D | | C04679 | =B | D | | ALL |
| 0301 | 16 | | GA | | 6-0 | 24-51-11 | TB5003 | 6 | E | | C04221 | =B | D | * | ALL |
| 0304 | 16 | | GA | | 3-0 | 24-51-11 | C01226 | =B | D | | C04221 | =B | D | * | ALL |
| 0401 | 16 | | GA | | 6-0 | 24-51-11 | TB5003 | 7 | E | | C04207 | =B | D | | 001-099 |
| 0401 | 16 | | GA | | 5-0 | 24-51-11 | TB5003 | 7 | E | | C04207 | =B | D | | 115-199 |
| 0403 | 16 | | GA | | 4-0 | 24-51-11 | C00667 | =B | D | | C01430 | =B | D | | 001-099 |
| 0403 | 16 | | GA | | 2-0 | 24-51-11 | C00667 | =B | D | | C04087 | =B | D | * | 115-199 |
| 0404 | 16 | | GA | | 4-0 | 24-51-11 | C04087 | =B | D | * | C01276 | =B | D | | 115-199 |
| 0414 | 16 | | GA | | 2-0 | 24-51-11 | C01276 | =B | D | | C00709 | =B | D | * | 001-099 |
| 0414 | 16 | | GA | | 3-0 | 24-51-11 | C01430 | =B | D | * | C00709 | =B | D | | 115-199 |
| 0415 | 16 | | GA | | 2-0 | 24-51-11 | C00709 | =B | D | * | C01271 | =B | D | | 001-099 |
| 0501 | 10 | | HA | | 5-1 | 24-51-13 | TB5003 | 1 | E | | C03003 | A2 | D | | 001-099 |
| 0501 | 08 | | HA | | 5-3 | 24-51-13 | TB5003 | 1 | E | | C03004 | A2 | D | | 115-199 |
| 0502 | 10 | | HA | | 5-0 | 24-51-13 | TB5003 | 2 | E | | C03003 | B2 | D | | 001-099 |
| 0502 | 08 | | HA | | 4-7 | 24-51-13 | TB5003 | 2 | E | | C03004 | B2 | D | | 115-199 |
| 0503 | 10 | | HA | | 5-0 | 24-51-13 | TB5003 | 3 | E | | C03003 | C2 | D | | 001-099 |
| 0503 | 08 | | HA | | 5-3 | 24-51-13 | TB5003 | 3 | E | | C03004 | C2 | D | | 115-199 |
| 0504 | 12 | | HA | | 1-6 | 24-54-11 | C00670 | =B | D | | C04224 | =B | D | | 001-099 |
| 0504 | 08 | | HA | | 1-6 | 24-54-11 | C00670 | =B | D | | C04224 | =B | D | | 115-199 |
| 0630 | 16 | | GA | | 4-0 | 24-51-11 | C04280 | =B | D | * | C04081 | =B | D | * | 115-199 |
| 0631 | 16 | | GA | | 3-0 | 24-51-11 | C04103 | =B | D | | C04081 | =B | D | * | 115-199 |
| 0632 | 14 | | GA | | 3-0 | 24-53-11 | C01080 | =B | D | | C01180 | =B | D | | ALL |
| 0641 | 16 | | GA | | 2-0 | 24-54-11 | C04069 | =B | D | | C04059 | =B | D | | 115-199 |
| 0650 | 16 | | GA | | 4-0 | 24-51-11 | C01249 | =B | D | | C01464 | =B | D | | ALL |
| 0661 | 16 | | GA | | 4-0 | 24-51-11 | C01247 | =B | D | | C01430 | =B | D | * | 115-199 |
| ZZAA | 02 | | ZB | | 0-0 | 24-54-11 | C01171 | =B | D | | C04178 | =B | D | | 001-099 |
| ZZAA | 05 | | ZB | | 0-0 | 24-54-11 | C01171 | =B | D | | C01176 | =B | D | | 115-199 |
| ZZAC | 04 | | ZB | | 0-0 | 24-54-11 | C01400 | =B | D | | C04126 | =B | D | | 001-099 |
| ZZAC | 04 | | ZB | | 5-0 | 24-54-11 | C01400 | =B | D | | C04126 | =B | D | | 115-199 |
| ZZAD | 02 | | ZB | | 0-0 | 24-54-11 | C04129 | =B | D | | C04119 | =B | D | | 001-099 |
| ZZAD | 00 | | ZB | | 0-0 | 24-54-11 | C01182 | =B | D | | C01176 | =B | D | | 115-199 |
| ZZAJ | 02 | | ZB | | 0-0 | 24-54-11 | C04375 | =B | D | | C04376 | =B | D | | ALL |
| ZZAQ | 03 | | ZB | | 0-0 | 24-54-11 | C04024 | =B | D | | C04044 | =B | D | | ALL |
| ZZAS | 02 | | ZB | | 0-0 | 24-54-11 | C01143 | =B | D | | C01136 | =B | D | | ALL |
| ZZAT | 02 | | ZB | | 0-0 | 24-54-11 | C04270 | =B | D | | C04032 | =B | D | | 001-099 |
| ZZAT | 02 | | ZB | | 0-0 | 24-54-11 | C01128 | =B | D | | C04308 | =B | D | | 115-199 |
| ZZCA | 02 | | ZB | | 0-0 | 24-53-11 | C01080 | =B | D | | C01082 | =B | D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0112 | 286N0112 | | | P11-3 MODULE WIRING - LEFT BUSSES (continued) | | | | | | | | | | | |
| ZZCD | 02 | | ZB | | 0-0 | 24-53-11 | C04099 | | =B | D | C04101 | | =B | D | ALL |
| ZZFC | 02 | | ZB | | 0-0 | 24-54-11 | C00660 | | =B | D | C00670 | | =B | D | ALL |
| ZZFG | 02 | | ZB | | 0-0 | 24-54-11 | C04270 | | =B | D | C04032 | | =B | D | 115-199 |
| ZZHH | 02 | | ZB | | 0-0 | 24-54-11 | C04071 | | =B | D | C04059 | | =B | D | 001-099 |
| ZZHH | 02 | | ZB | | 0-0 | 24-54-11 | C04071 | | =B | D | C04069 | | =B | D | 115-199 |
| ZZOA | 00 | | ZB | | 0-0 | 24-54-11 | C01171 | | =B | D | C04178 | | =B | D | 115-199 |
| ZZOB | 00 | | ZB | | 0-0 | 24-54-11 | C01181 | | =B | D | C04178 | | =B | D | 115-199 |
| ZZOC | 00 | | ZB | | 0-0 | 24-54-11 | C01181 | | =B | D | C01182 | | =B | D | 115-199 |
| ZZOD | 02 | | ZB | | 0-0 | 24-54-11 | C01182 | | =B | D | C01176 | | =B | D | 001-099 |
| ZZOE | 00 | | ZB | | 0-0 | 24-54-11 | C01400 | | =B | D | C00822 | | =B | D | 115-199 |
| ZZOF | 00 | | ZB | | 0-0 | 24-54-11 | C00824 | | =B | D | C00822 | | =B | D | 115-199 |
| ZZOG | 00 | | ZB | | 0-0 | 24-54-11 | C01400 | | =B | D | C00822 | | =B | D | 001-099 |
| ZZOG | 00 | | ZB | | 0-0 | 24-54-11 | C00824 | | =B | D | C04126 | | =B | D | 115-199 |
| ZZOH | 00 | | ZB | | 0-0 | 24-54-11 | C00824 | | =B | D | C00822 | | =B | D | 001-099 |
| ZZOI | 00 | | ZB | | 0-0 | 24-54-11 | C00824 | | =B | D | C04126 | | =B | D | 001-099 |
| ZZOL | 00 | | ZB | | 0-0 | 24-54-11 | C04044 | | =B | D | C04043 | | =B | D | 115-199 |
| ZZOM | 00 | | ZB | | 0-0 | 24-54-11 | C04024 | | =B | D | C04043 | | =B | D | 115-199 |
| ZZON | 00 | | ZB | | 0-0 | 24-54-11 | C04044 | | =B | D | C04043 | | =B | D | 001-099 |
| ZZOP | 00 | | ZB | | 0-0 | 24-54-11 | C04024 | | =B | D | C04043 | | =B | D | 001-099 |
| ZZOS | 02 | | ZB | | 0-0 | 24-54-11 | C04308 | | =B | D | C01128 | | =B | D | 001-099 |
| ZZXA | 02 | | ZA | | 0-0 | 24-54-11 | C01022 | | =B | D | C01412 | | =B | D | 115-199 |
| ZZXB | 02 | | ZA | | 0-0 | 24-54-11 | C04107 | | =B | D | C04119 | | =B | D | 115-199 |
| ZZXC | 02 | | ZA | | 0-0 | 24-54-11 | C04196 | | =B | D | C04019 | | =B | D | 001-099 |
| ZZXC | 02 | | ZA | | 3-0 | 24-54-11 | C04196 | | =B | D | C04019 | | =B | D | 115-199 |
| ZZXD | 02 | | ZA | | 0-0 | 24-54-11 | C01182 | | =B | D | C04178 | | =B | D | 001-099 |
| ZZXG | 02 | | ZA | | 0-0 | 24-53-11 | C01082 | | =B | D | C01005 | | =B | D | 001-099 |
| ZZXG | 02 | | ZA | | 3-0 | 24-53-11 | C01082 | | =B | D | C01005 | | =B | D | 115-199 |
| ZZXH | 02 | | ZA | | 0-0 | 24-51-11 | C01244 | | =B | D | C01249 | | =B | D | ALL |
| ZZXJ | 02 | | ZA | | 0-0 | 24-51-11 | C01464 | | =B | D | C04078 | | =B | D | 001-099 |
| ZZXJ | 02 | | ZA | | 3-0 | 24-51-11 | C01464 | | =B | D | C04078 | | =B | D | 115-199 |
| ZZXK | 02 | | ZA | | 0-0 | 24-54-11 | C04196 | | =B | D | C04308 | | =B | D | 001-099 |
| ZZXM | 02 | | ZA | | 0-0 | 24-54-11 | C00743 | | =B | D | C00822 | | =B | D | ALL |
| ZZXP | 02 | | ZA | | 0-0 | 24-54-11 | C04044 | | =B | D | C04071 | | =B | D | 001-099 |
| ZZXR | 02 | | ZA | | 0-0 | 24-54-11 | C04376 | | =B | D | C01254 | | =B | D | 001-099 |
| ZZXR | 02 | | ZA | | 0-0 | 24-54-11 | C04375 | | =B | D | C04107 | | =B | D | 115-199 |
| ZZXV | 02 | | ZA | | 0-0 | 24-53-11 | C01005 | | =B | D | C04099 | | =B | D | 001-099 |
| ZZXV | 02 | | ZA | | 4-0 | 24-53-11 | C01005 | | =B | D | C04099 | | =B | D | 115-199 |
| ZZXZ | 02 | | ZA | | 0-0 | 24-51-11 | C04207 | | =B | D | C00667 | | =B | D | 001-099 |
| ZZXZ | 02 | | ZA | | 3-0 | 24-51-11 | C04207 | | =B | D | C00667 | | =B | D | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------|-------|--|--------|------|------|--------|--------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0112 | 286N0112 | | | | | P11-3 MODULE WIRING - LEFT BUSSES (continued) | | | | | | | | | |
| | ZZYA | 02 | ZA | | 0-0 | 24-51-11 | C01276 | =B | D | | C01247 | =B | D | | ALL |
| | ZZYE | 02 | ZA | | 0-0 | 24-51-11 | C04103 | =B | D | | C04081 | =B | D | | 001-099 |
| | ZZYF | 02 | ZA | | 0-0 | 24-51-11 | C01247 | =B | D | | C01430 | =B | D | | 001-099 |
| | ZZYH | 02 | ZA | | 0-0 | 24-54-11 | C04129 | =B | D | | C04107 | =B | D | | 001-099 |
| | ZZYH | 02 | ZA | | 0-0 | 24-54-11 | C04107 | =B | D | | C04129 | =B | D | | 115-199 |
| | ZZYJ | 02 | ZA | | 0-0 | 24-51-15 | C01241 | =B | D | | C01242 | =B | D | | ALL |
| | ZZYK | 02 | ZA | | 0-0 | 24-51-15 | C04038 | =B | D | | C00673 | =B | D | | 001-099 |
| | ZZYK | 02 | ZA | | 0-0 | 24-51-15 | C00673 | =B | D | | C04038 | =B | D | | 115-199 |
| | ZZYT | 02 | ZA | | 0-0 | 24-51-13 | C03003 | A2 | D | | C03004 | A2 | D | | ALL |
| | ZZYW | 02 | ZA | | 0-0 | 24-51-13 | C03003 | B2 | D | | C03004 | B2 | D | | ALL |
| | ZZYX | 02 | ZA | | 0-0 | 24-51-13 | C03003 | C2 | D | | C03004 | C2 | D | | ALL |
| | ZZZA | 02 | ZA | | 0-0 | 24-54-11 | C01022 | =B | D | | C01035 | =B | D | | ALL |
| | ZZZB | 02 | ZA | | 0-0 | 24-54-11 | C01035 | =B | D | | C04032 | =B | D | | ALL |
| | ZZZC | 02 | ZA | | 0-0 | 24-54-11 | C01254 | =B | D | | C04376 | =B | D | | 115-199 |
| | ZZZD | 02 | ZA | | 0-0 | 24-54-11 | C04069 | =B | D | | C00705 | =B | D | | 001-099 |
| | ZZZD | 02 | ZA | | 0-0 | 24-54-11 | C04059 | =B | D | | C00705 | =B | D | | 115-199 |
| | ZZZE | 02 | ZA | | 0-0 | 24-51-13 | C03004 | A2 | D | | C03043 | A2 | D | | 001-099 |
| | ZZZF | 02 | ZA | | 0-0 | 24-51-13 | C03004 | B2 | D | | C03043 | B2 | D | | 001-099 |
| | ZZZG | 02 | ZA | | 0-0 | 24-51-13 | C03004 | C2 | D | | C03043 | C2 | D | | 001-099 |
| | ZZZN | 02 | ZA | | 0-0 | 24-51-11 | C01244 | =B | D | | C01226 | =B | D | | ALL |
| | ZZZT | 02 | ZA | | 0-0 | 24-54-11 | C01332 | =B | D | | C04019 | =B | D | | ALL |
| | ZZZU | 02 | ZA | | 0-0 | 24-54-11 | C00670 | =B | D | | C01332 | =B | D | | 115-199 |
| | ZZZV | 02 | ZA | | 0-0 | 24-54-11 | C01290 | =B | D | | C01298 | =B | D | | ALL |
| | ZZZW | 02 | ZA | | 0-0 | 24-54-11 | C01332 | =B | D | | C00660 | =B | D | | 001-099 |
| | ZZZY | 02 | ZA | | 0-0 | 24-54-11 | C04375 | =B | D | | C00705 | =B | D | | ALL |
| W0114 | 286N0114 | | | | | P11-2 MODULE WIRING - RIGHT - STBY - CTR - BUSSES | | | | | | | | | |
| | 0001 | 08 | HA | | 7-7 | 24-54-21 | TB5004 | 4 | E | | C00568 | =B | KA | * | 001-099 |
| | 0001 | 08 | HA | | 7-10 | 24-54-21 | TB5004 | 4 | E | | C00568 | =B | KA | * | 115-199 |
| | 0002 | 08 | HA | | 3-0 | 24-54-21 | C00568 | =B | KA | * | C00545 | =B | D | | 001-008 |
| | 0002 | 08 | HA | | 3-4 | 24-54-21 | C00568 | =B | KA | * | C00545 | =B | D | | 009-099 |
| | 0002 | 08 | HA | | 3-3 | 24-54-21 | C00568 | =B | KA | * | C00545 | =B | D | | 115-199 |
| | 0003 | 12 | HA | | 1-5 | 24-54-21 | C04034 | =B | D | | C04212 | =B | D | | 001-099 |
| | 0003 | 12 | HA | | 1-4 | 24-54-21 | C04034 | =B | D | | C04212 | =B | D | | 115-199 |
| | 0006 | 12 | HA | | 1-1 | 24-54-21 | C01540 | =B | D | | C00623 | =B | D | * | 001-008 |
| | 0006 | 12 | HA | | 1-2 | 24-54-21 | C01540 | =B | D | | C00623 | =B | D | * | 009-099 |
| | 0006 | 12 | HA | | 1-0 | 24-54-21 | C01540 | =B | D | | C00623 | =B | D | * | 115-199 |
| | 0008 | 12 | HA | | 1-3 | 24-54-21 | C01561 | =B | D | | C04258 | =B | D | | 115-199 |
| | 0012 | 22 | GA | | 8-0 | 24-51-72 | C00587 | =B | D | | TB5002 | 6 | E | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0114 | 286N0114 | | | P11-2 MODULE WIRING - RIGHT - STBY - CTR - BUSSES (continued) | | | | | | | | | | | |
| 0012 | 22 | | GA | | 7-0 | 24-51-72 | TB5002 | 6 | E | | C00587 | =B | D | | 115-199 |
| 0014 | 22 | | GA | | 8-0 | 24-51-72 | C00589 | =B | D | | TB5002 | 5 | E | | 001-099 |
| 0014 | 22 | | GA | | 7-0 | 24-51-72 | C00589 | =B | D | | TB5002 | 5 | E | | 115-199 |
| 0016 | 22 | | GA | | 8-0 | 24-51-72 | C00634 | =B | D | * | TB5002 | 7 | E | | 001-099 |
| 0016 | 22 | | GA | | 7-0 | 24-51-72 | TB5002 | 7 | E | | C00634 | =B | D | | 115-199 |
| 0017 | 22 | | GA | | 3-0 | 24-51-72 | C00634 | =B | D | * | C00638 | =B | D | | 001-099 |
| 0017 | 22 | | GA | | 3-0 | 24-51-72 | C00638 | =B | D | | C00634 | =B | D | | 115-199 |
| 0018 | 22 | | GA | | 3-0 | 24-51-72 | C00626 | =B | D | | C00605 | =B | D | | 001-099 |
| 0018 | 22 | | GA | | 3-0 | 24-51-72 | C00626 | =B | D | | C04601 | =B | D | | 115-199 |
| 0021 | 16 | | GA | | 4-0 | 24-51-22 | C03006 | A2 | D | | C00514 | =B | D | * | ALL |
| 0024 | 16 | | GA | | 2-0 | 24-51-22 | C01535 | =B | D | * | C04210 | =B | D | | ALL |
| 0026 | 12 | | HA | | 2-0 | 24-54-21 | C00623 | =B | D | * | C04423 | =B | D | | 001-008, 115-199 |
| 0026 | 12 | | HA | | 2-5 | 24-54-21 | C00623 | =B | D | * | C04423 | =B | D | | 009-099 |
| 0029 | 16 | | GA | | 2-0 | 24-51-22 | C00598 | =B | D | * | C00514 | =B | D | * | ALL |
| 0030 | 16 | | GA | | 3-0 | 24-51-22 | C01535 | =B | D | * | C00598 | =B | D | * | ALL |
| 0031 | 12 | | HA | | 7-5 | 24-54-21 | TB5004 | 5 | E | | C00560 | =B | D | | 001-008 |
| 0031 | 12 | | HA | | 7-4 | 24-54-21 | TB5004 | 5 | E | | C00560 | =B | D | | 009-099 |
| 0034 | 18 | | GA | | 3-0 | 24-54-71 | C01481 | =B | D | | C04478 | =B | D | | 001-099 |
| 0035 | 18 | | GA | | 2-0 | 24-54-71 | C04485 | =B | D | | C04476 | =B | D | | 009-099 |
| 0036 | 12 | | HA | | 7-4 | 24-51-52 | C00630 | =B | D | | TB5004 | 11 | E | | 009-099 |
| 0042 | 16 | | GA | | 4-0 | 24-51-22 | C00583 | =B | D | | C00532 | =B | D | | 115-199 |
| 0051 | 16 | | GA | | 4-0 | 24-51-22 | C03006 | C2 | D | * | C00596 | =B | D | | 001-099 |
| 0051 | 16 | | GA | | 4-0 | 24-51-22 | C03006 | C2 | D | | C00596 | =B | D | | 115-199 |
| 0061 | 12 | | HA | | 7-7 | 24-54-21 | TB5004 | 5 | E | | C00560 | =B | D | | 115-199 |
| 0071 | 14 | | GA | | 6-0 | 24-53-21 | TB5002 | 4 | E | | C01009 | =B | D | * | ALL |
| 0072 | 14 | | GA | | 2-0 | 24-53-21 | C01009 | =B | D | * | C01038 | =B | D | | ALL |
| 0101 | 16 | | GA | | 4-0 | 24-51-22 | C00532 | =B | D | | C00583 | =B | D | | 001-099 |
| 0102 | 16 | | GA | | 2-0 | 24-51-22 | C04052 | =B | D | | C00612 | =B | D | | ALL |
| 0301 | 16 | | GA | | 8-0 | 24-51-22 | TB5002 | 1 | E | | C03006 | A2 | D | * | ALL |
| 0302 | 16 | | GA | | 8-0 | 24-51-22 | TB5002 | 2 | E | | C03006 | B2 | D | | ALL |
| 0303 | 16 | | HA | | 8-0 | 24-51-22 | TB5002 | 3 | E | | C03006 | C2 | D | * | 001-099 |
| 0303 | 16 | | GA | | 8-0 | 24-51-22 | TB5002 | 3 | E | | C03006 | C2 | D | | 115-199 |
| 0701 | 08 | | HA | | 7-0 | 24-54-71 | TB5006 | 4 | E | | C01051 | =B | D | | 001-002 |
| 0701 | 08 | | HA | | 6-11 | 24-54-71 | TB5006 | 4 | E | | C01051 | =B | D | | 003-008 |
| 0701 | 08 | | HA | | 7-0 | 24-54-71 | TB5006 | 4 | E | | C04485 | =B | D | | 009-099 |
| 0801 | 18 | | GA | | 7-0 | 24-51-31 | C00524 | =B | D | | TB5006 | 3 | E | | 001-099 |
| 0802 | 22 | | GA | | 7-0 | 24-51-31 | C00613 | =B | D | | TB5006 | 2 | E | | 001-099 |
| ZZAA | 02 | | ZB | | 0-0 | 24-54-21 | C00623 | =B | D | | C04240 | =B | D | | 115-199 |
| ZZAB | 03 | | ZB | | 0-0 | 24-51-72 | C00594 | =B | D | | C00581 | =B | D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0114 | 286N0114 | | | P11-2 MODULE WIRING - RIGHT - STBY - CTR - BUSSES (continued) | | | | | | | | | | | |
| ZZAC | 00 | | ZB | | 0-0 | 24-54-71 | C01511 | =B | D | | C04113 | =B | D | | 001-099 |
| ZZAD | 02 | | ZB | | 0-0 | 24-51-72 | C00626 | =B | D | | C00638 | =B | D | | ALL |
| ZZAE | 00 | | ZB | | 0-0 | 24-54-71 | C04113 | =B | D | | C04114 | =B | D | | 001-099 |
| ZZAF | 04 | | ZB | | 0-0 | 24-54-21 | C01532 | =B | D | | C00545 | =B | D | | ALL |
| ZZAG | 02 | | ZB | | 0-0 | 24-54-21 | C01561 | =B | D | | C00640 | =B | D | | 001-099 |
| ZZAG | 02 | | ZB | | 0-0 | 24-54-21 | C01561 | =B | D | | C00726 | =B | D | | 115-199 |
| ZZAH | 00 | | ZB | | 0-0 | 24-54-71 | C04114 | =B | D | | C04151 | =B | D | | 001-099 |
| ZZAJ | 04 | | ZB | | 0-0 | 24-54-71 | C04085 | =B | D | | C00551 | =B | D | | 001-099 |
| ZZAK | 02 | | ZB | | 0-0 | 24-54-71 | C04275 | =B | D | | C01321 | =B | D | | 001-099 |
| ZZAR | 02 | | ZB | | 0-0 | 24-53-21 | C01526 | =B | D | | C01038 | =B | D | | ALL |
| ZZBA | 02 | | ZB | | 0-0 | 24-54-21 | C04212 | =B | D | | C04271 | =B | D | | ALL |
| ZZBB | 02 | | ZB | | 0-0 | 24-54-21 | C00560 | =B | D | | C04364 | =B | D | | ALL |
| ZZBD | 00 | | ZB | | 0-0 | 24-54-71 | C01010 | =B | D | | C00774 | =B | D | | 001-099 |
| ZZCB | 06 | | ZB | | 0-0 | 24-54-71 | C04054 | =B | D | | C01051 | =B | D | | 001-008 |
| ZZCB | 06 | | ZB | | 0-0 | 24-54-71 | C04054 | =B | D | | C04485 | =B | D | | 009-099 |
| ZZCE | 04 | | ZB | | 0-0 | 24-54-71 | C01148 | =B | D | | C00552 | =B | D | | 001-099 |
| ZZCF | 08 | | ZB | | 0-0 | 24-54-71 | C01310 | =B | D | | C01132 | =B | D | | 001-099 |
| ZZCG | 09 | | ZB | | 0-0 | 24-54-71 | C01010 | =B | D | | C00788 | =B | D | | 001-099 |
| ZZCJ | 04 | | ZB | | 0-0 | 24-54-71 | C01322 | =B | D | | C04037 | =B | D | | 001-099 |
| ZZCK | 08 | | ZB | | 0-0 | 24-54-71 | C00703 | =B | D | | C01306 | =B | D | | 001-099 |
| ZZCM | 07 | | ZB | | 0-0 | 24-54-71 | C04290 | =B | D | | C01481 | =B | D | | 001-099 |
| ZZCO | 05 | | ZB | | 0-0 | 24-54-71 | C04151 | =B | D | | C01510 | =B | D | | 001-099 |
| ZZDA | 00 | | ZB | | 0-0 | 24-54-71 | C01510 | =B | D | | C01511 | =B | D | | 001-099 |
| ZZDB | 03 | | ZB | | 0-0 | 24-51-31 | C00613 | =B | D | | C01525 | =B | D | | 001-099 |
| ZZMA | 02 | | ZB | | 0-0 | 24-54-71 | C04476 | =B | D | | C04477 | =B | D | | 009-099 |
| ZZNB | 00 | | ZB | | 0-0 | 24-54-71 | C01310 | =B | D | | C01303 | =B | D | | 001-099 |
| ZZND | 00 | | ZB | | 0-0 | 24-54-71 | C04251 | =B | D | | C01483 | =B | D | | 001-099 |
| ZZNF | 00 | | ZB | | 0-0 | 24-54-71 | C01303 | =B | D | | C01048 | =B | D | | 001-099 |
| ZZNG | 00 | | ZB | | 0-0 | 24-54-71 | C01175 | =B | D | | C01132 | =B | D | | 001-099 |
| ZZNH | 00 | | ZB | | 0-0 | 24-54-71 | C01325 | =B | D | | C04037 | =B | D | | 001-099 |
| ZZNJ | 00 | | ZB | | 0-0 | 24-54-71 | C01121 | =B | D | | C00548 | =B | D | | 001-099 |
| ZZOA | 00 | | ZB | | 0-0 | 24-51-31 | C00613 | =B | D | | C00602 | =B | D | | 001-099 |
| ZZOA | 00 | | ZB | | 0-0 | 24-54-21 | C00545 | =B | D | | C04258 | =B | D | | 115-199 |
| ZZOB | 00 | | ZB | | 0-0 | 24-51-31 | C01525 | =B | D | | C00602 | =B | D | | 001-099 |
| ZZOB | 00 | | ZB | | 0-0 | 24-54-21 | C04258 | =B | D | | C04256 | =B | D | | 115-199 |
| ZZOC | 00 | | ZB | | 0-0 | 24-54-71 | C00704 | =B | D | | C01214 | =B | D | | 001-099 |
| ZZOC | 00 | | ZB | | 0-0 | 24-54-21 | C04256 | =B | D | | C01532 | =B | D | | 115-199 |
| ZZOD | 00 | | ZB | | 0-0 | 24-51-72 | C00594 | =B | D | | C00585 | =B | D | | ALL |
| ZZOE | 00 | | ZB | | 0-0 | 24-51-72 | C00585 | =B | D | | C00581 | =B | D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0114 | 286N0114 | | | P11-2 MODULE WIRING - RIGHT - STBY - CTR - BUSSES (continued) | | | | | | | | | | | |
| ZZOF | 00 | | ZB | | 0-0 | 24-54-21 | C00545 | =B | D | | C00557 | =B | D | | 001-099 |
| ZZOG | 00 | | ZB | | 0-0 | 24-54-21 | C00557 | =B | D | | C00554 | =B | D | | 001-099 |
| ZZOH | 00 | | ZB | | 0-0 | 24-54-21 | C00554 | =B | D | | C01532 | =B | D | | 001-099 |
| ZZOK | 00 | | ZB | | 0-0 | 24-54-71 | C00703 | =B | D | | C00704 | =B | D | | 001-099 |
| ZZOL | 00 | | ZB | | 0-0 | 24-54-71 | C00553 | =B | D | | C01147 | =B | D | | 001-099 |
| ZZOM | 00 | | ZB | | 0-0 | 24-54-71 | C00553 | =B | D | | C00552 | =B | D | | 001-099 |
| ZZON | 00 | | ZB | | 0-0 | 24-54-71 | C01306 | =B | D | | C01308 | =B | D | | 001-099 |
| ZZOP | 00 | | ZB | | 0-0 | 24-54-71 | C00784 | =B | D | | C00775 | =B | D | | 001-099 |
| ZZOQ | 00 | | ZB | | 0-0 | 24-54-71 | C00783 | =B | D | | C00775 | =B | D | | 001-099 |
| ZZOR | 00 | | ZB | | 0-0 | 24-54-71 | C00783 | =B | D | | C00774 | =B | D | | 001-099 |
| ZZOS | 00 | | ZB | | 0-0 | 24-54-71 | C01307 | =B | D | | C01214 | =B | D | | 001-099 |
| ZZOT | 00 | | ZB | | 0-0 | 24-54-71 | C01325 | =B | D | | C01323 | =B | D | | 001-099 |
| ZZOU | 00 | | ZB | | 0-0 | 24-54-71 | C01322 | =B | D | | C01323 | =B | D | | 001-099 |
| ZZOV | 00 | | ZB | | 0-0 | 24-54-71 | C01048 | =B | D | | C01058 | =B | D | | 001-099 |
| ZZOW | 00 | | ZB | | 0-0 | 24-54-71 | C01183 | =B | D | | C01175 | =B | D | | 001-099 |
| ZZOX | 00 | | ZB | | 0-0 | 24-54-71 | C04251 | =B | D | | C04252 | =B | D | | 001-099 |
| ZZOY | 00 | | ZB | | 0-0 | 24-54-71 | C00796 | =B | D | | C04252 | =B | D | | 001-099 |
| ZZOZ | 00 | | ZB | | 0-0 | 24-54-71 | C00796 | =B | D | | C01390 | =B | D | | 001-099 |
| ZZPA | 00 | | ZB | | 0-0 | 24-54-71 | C04290 | =B | D | | C01390 | =B | D | | 001-099 |
| ZZPB | 00 | | ZB | | 0-0 | 24-54-71 | C00551 | =B | D | | C00548 | =B | D | | 001-099 |
| ZZPD | 00 | | ZB | | 0-0 | 24-54-71 | C01121 | =B | D | | C04085 | =B | D | | 001-099 |
| ZZPF | 00 | | ZB | | 0-0 | 24-54-71 | C04132 | =B | D | | C04133 | =B | D | | 001-099 |
| ZZPG | 00 | | ZB | | 0-0 | 24-54-71 | C04133 | =B | D | | C04175 | =B | D | | 001-099 |
| ZZPH | 00 | | ZB | | 0-0 | 24-54-71 | C04054 | =B | D | | C04175 | =B | D | | 001-099 |
| ZZPI | 00 | | ZB | | 0-0 | 24-54-71 | C04025 | =B | D | | C04023 | =B | D | | 001-099 |
| ZZPJ | 04 | | ZB | | 0-0 | 24-54-71 | C04061 | =B | D | | C04025 | =B | D | | 001-099 |
| ZZPK | 00 | | ZB | | 0-0 | 24-54-71 | C01483 | =B | D | | C01481 | =B | D | | 001-099 |
| ZZPL | 00 | | ZB | | 0-0 | 24-54-71 | C00772 | =B | D | | C00788 | =B | D | | 001-099 |
| ZZPM | 00 | | ZB | | 0-0 | 24-54-71 | C00784 | =B | D | | C00776 | =B | D | | 001-099 |
| ZZPN | 00 | | ZB | | 0-0 | 24-54-71 | C00785 | =B | D | | C00776 | =B | D | | 001-099 |
| ZZPO | 00 | | ZB | | 0-0 | 24-54-71 | C00785 | =B | D | | C00772 | =B | D | | 001-099 |
| ZZPP | 00 | | ZB | | 0-0 | 24-54-71 | C01308 | =B | D | | C01201 | =B | D | | 001-099 |
| ZZPQ | 00 | | ZB | | 0-0 | 24-54-71 | C01200 | =B | D | | C01201 | =B | D | | 001-099 |
| ZZPR | 00 | | ZB | | 0-0 | 24-54-71 | C01200 | =B | D | | C01307 | =B | D | | 001-099 |
| ZZPS | 00 | | ZB | | 0-0 | 24-54-71 | C01051 | =B | D | | C01052 | =B | D | | 001-008 |
| ZZPS | 00 | | ZB | | 0-0 | 24-54-71 | C04485 | =B | D | | C01052 | =B | D | | 009-099 |
| ZZPT | 00 | | ZB | | 0-0 | 24-54-71 | C04132 | =B | D | | C01052 | =B | D | | 001-099 |
| ZZPU | 00 | | ZB | | 0-0 | 24-54-71 | C04061 | =B | D | | C04216 | =B | D | | 001-099 |
| ZZPV | 00 | | ZB | | 0-0 | 24-54-71 | C04023 | =B | D | | C04216 | =B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0114 | 286N0114 | P11-2 MODULE WIRING - RIGHT - STBY - CTR - BUSSES (continued) | | | | | | | | | | | | | |
| ZZPW | 00 | | ZB | | 0-0 | 24-54-71 | C01058 | =B | D | | C01184 | =B | D | | 001-099 |
| ZZPX | 00 | | ZB | | 0-0 | 24-54-71 | C01183 | =B | D | | C01184 | =B | D | | 001-099 |
| ZZPY | 00 | | ZB | | 0-0 | 24-54-71 | C01148 | =B | D | | C01147 | =B | D | | 001-099 |
| ZZXA | 02 | | ZA | | 0-0 | 24-54-21 | C00517 | =B | D | | C00523 | =B | D | | 115-199 |
| ZZXB | 02 | | ZA | | 0-0 | 24-54-71 | C04061 | =B | D | | C04151 | =B | D | | 001-099 |
| ZZXC | 02 | | ZA | | 0-0 | 24-54-71 | C01321 | =B | D | | C00783 | =B | D | | 001-099 |
| ZZXD | 02 | | ZA | | 0-0 | 24-54-71 | C01308 | =B | D | | C01390 | =B | D | | 001-099 |
| ZZXE | 02 | | ZA | | 0-0 | 24-54-71 | C00551 | =B | D | | C00784 | =B | D | | 001-099 |
| ZZXF | 02 | | ZA | | 0-0 | 24-54-71 | C00796 | =B | D | | C01058 | =B | D | | 001-099 |
| ZZXG | 02 | | ZA | | 0-0 | 24-54-71 | C01184 | =B | D | | C04132 | =B | D | | 001-099 |
| ZZXH | 02 | | ZA | | 0-0 | 24-54-71 | C01147 | =B | D | | C04216 | =B | D | | 001-099 |
| ZZXJ | 02 | | ZA | | 0-0 | 24-54-71 | C01323 | =B | D | | C00775 | =B | D | | 001-099 |
| ZZXK | 02 | | ZA | | 0-0 | 24-54-71 | C01511 | =B | D | | C04085 | =B | D | | 001-099 |
| ZZYA | 02 | | ZA | | 0-0 | 24-54-21 | C01561 | =B | D | | C00517 | =B | D | | ALL |
| ZZYB | 02 | | ZA | | 0-0 | 24-54-21 | C00517 | =B | D | | C00523 | =B | D | | 001-099 |
| ZZYC | 02 | | ZA | | 0-0 | 24-54-71 | C04054 | =B | D | | C04025 | =B | D | | 001-099 |
| ZZYD | 02 | | ZA | | 0-0 | 24-51-72 | C00589 | =B | D | | C00594 | =B | D | | ALL |
| ZZYE | 02 | | ZA | | 0-0 | 24-51-22 | C00636 | =B | D | | C04210 | =B | D | | 001-099 |
| ZZYH | 02 | | ZA | | 0-0 | 24-54-21 | C04212 | =B | D | | C01018 | =B | D | | ALL |
| ZZYJ | 02 | | ZA | | 0-0 | 24-51-72 | C00601 | =B | D | | C00587 | =B | D | | ALL |
| ZZYK | 02 | | ZA | | 0-0 | 24-51-22 | C03006 | B2 | D | | C00532 | =B | D | | ALL |
| ZZYL | 02 | | ZA | | 0-0 | 24-51-22 | C00612 | =B | D | | C04260 | =B | D | | 115-199 |
| ZZYM | 02 | | ZA | | 0-0 | 24-54-21 | C04034 | =B | D | | C04256 | =B | D | | 115-199 |
| ZZYN | 02 | | ZA | | 0-0 | 24-54-21 | C01018 | =B | D | | C01540 | =B | D | | ALL |
| ZZYP | 02 | | ZA | | 0-0 | 24-51-22 | C00596 | =B | D | | C00610 | =B | D | | ALL |
| ZZYQ | 02 | | ZA | | 0-0 | 24-51-22 | C04052 | =B | D | | C00610 | =B | D | | ALL |
| ZZYW | 02 | | ZA | | 0-0 | 24-54-21 | C04034 | =B | D | | C00554 | =B | D | | 001-099 |
| ZZYX | 02 | | ZA | | 0-0 | 24-54-21 | C00557 | =B | D | | C00640 | =B | D | | 001-099 |
| ZZZA | 02 | | ZA | | 0-0 | 24-51-31 | C00515 | =B | D | | C00602 | =B | D | | 001-099 |
| W0116 | 286N0116 | P11-4 MODULE WIRING - RIGHT BUSSES | | | | | | | | | | | | | |
| 0001 | 08 | | HA | | 5-0 | 24-54-21 | TB5004 | 5 | E | | C01173 | =B | D | | 001-099 |
| 0001 | 08 | | HA | | 4-0 | 24-54-21 | TB5004 | 5 | E | | C01173 | =B | D | | 115-199 |
| 0011 | 16 | | GA | | 4-0 | 24-51-21 | C04094 | =B | D | | C04104 | =B | D | * | ALL |
| 0013 | 12 | | HA | | 3-8 | 24-54-21 | C04108 | =B | D | | C01280 | =B | D | | 115-199 |
| 0016 | 12 | | HA | | 2-0 | 24-54-21 | C01302 | =B | D | | C01202 | =B | D | | 001-099 |
| 0019 | 12 | | HA | | 1-2 | 24-54-21 | C01053 | =B | D | | C04014 | =B | D | | 115-199 |
| 0023 | 16 | | GA | | 5-0 | 24-51-22 | C04227 | =B | D | * | C00565 | =B | D | | 001-099 |
| 0023 | 16 | | GA | | 8-0 | 24-51-22 | C04227 | =B | D | * | C00565 | =B | D | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Description | | | From | | | | To | | | | |
|------------------------|-------------|-------|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0116 | 286N0116 | | P11-4 MODULE WIRING - RIGHT BUSSES (continued) | | | | | | | | | | | |
| 0024 | 22 | GA | | 7-0 | 24-51-72 | TB5002 | 8 | E | | C04231 | =L | D | | 001-099 |
| 0024 | 16 | GA | | 8-0 | 24-51-72 | TB5002 | 8 | E | | C04231 | =L | D | | 115-199 |
| 0025 | 22 | GA | | 7-0 | 24-51-72 | TB5002 | 9 | E | | C04229 | =L | D | | 001-099 |
| 0025 | 16 | GA | | 8-0 | 24-51-72 | TB5002 | 9 | E | | C04229 | =L | D | | 115-199 |
| 0026 | 22 | GA | | 7-0 | 24-51-72 | TB5002 | 10 | E | | C04227 | =L | D | | 001-099 |
| 0026 | 16 | GA | | 8-0 | 24-51-72 | TB5002 | 10 | E | | C04227 | =L | D | | 115-199 |
| 0027 | 16 | GA | | 8-0 | 24-51-22 | C04231 | =B | D | | TB5002 | 3 | E | | ALL |
| 0028 | 16 | GA | | 8-0 | 24-51-22 | C04229 | =B | D | | TB5002 | 2 | E | | ALL |
| 0029 | 16 | GA | | 8-0 | 24-51-22 | C04227 | =B | D | * | TB5002 | 1 | E | | ALL |
| 0030 | 08 | HA | | 0-5 | 24-54-21 | C01174 | =B | D | | C01145 | =B | D | | ALL |
| 0031 | 16 | GA | | 2-0 | 24-51-21 | C04104 | =B | D | * | C04317 | =B | D | | ALL |
| 0036 | 08 | HA | | 2-3 | 24-54-21 | C01202 | =B | D | | C01273 | =B | D | | 115-199 |
| 0037 | 12 | HA | | 3-3 | 24-54-21 | C04130 | =B | D | | C04189 | =B | D | | 001-002 |
| 0040 | 12 | HA | | 6-4 | 24-51-25 | C00674 | =B | D | | TB5006 | 10 | E | | 001-099 |
| 0040 | 12 | HA | | 6-1 | 24-51-25 | C00674 | =B | D | | TB5006 | 10 | E | | 115-199 |
| 0041 | 12 | HA | | 6-8 | 24-51-25 | C04036 | =B | D | | TB5006 | 11 | E | | 001-099 |
| 0041 | 12 | HA | | 6-5 | 24-51-25 | C04036 | =B | D | | TB5006 | 11 | E | | 115-199 |
| 0042 | 12 | HA | | 5-10 | 24-51-25 | C04299 | =B | D | | TB5006 | 12 | E | | 001-099 |
| 0042 | 12 | HA | | 5-10 | 24-51-25 | C04299 | =B | D | * | TB5006 | 12 | E | | 115-199 |
| 0043 | 12 | HA | | 3-1 | 24-51-25 | C04299 | =B | D | | C01288 | =B | D | | 001-099 |
| 0043 | 12 | HA | | 2-11 | 24-51-25 | C04299 | =B | D | * | C01288 | =B | D | | 115-199 |
| 0100 | 12 | HA | | 2-0 | 24-54-21 | C04209 | =B | D | | C00765 | =B | D | | 001-099 |
| 0100 | 10 | HA | | 1-2 | 24-54-21 | C04209 | =B | D | | C00765 | =B | D | | 115-199 |
| 0101 | 14 | GA | | 8-0 | 24-53-21 | TB5002 | 4 | E | | C04183 | =B | D | | 001-099 |
| 0101 | 14 | GA | | 7-0 | 24-53-21 | TB5002 | 4 | E | | C04183 | =B | D | * | 115-199 |
| 0102 | 14 | GA | | 5-0 | 24-53-21 | C01287 | =B | D | | C04183 | =B | D | | 001-099 |
| 0102 | 14 | GA | | 4-0 | 24-53-21 | C01287 | =B | D | * | C01281 | =B | D | | 115-199 |
| 0103 | 14 | GA | | 4-0 | 24-53-21 | C01251 | =B | D | | C01499 | =B | D | * | ALL |
| 0104 | 14 | GA | | 2-0 | 24-53-21 | C01499 | =B | D | * | C01081 | =B | D | * | ALL |
| 0105 | 14 | GA | | 3-0 | 24-53-21 | C01081 | =B | D | * | C04100 | =B | D | | ALL |
| 0200 | 22 | GA | | 7-0 | 24-51-72 | C01239 | =B | D | | TB5002 | 6 | E | | 001-099 |
| 0200 | 22 | GA | | 7-0 | 24-51-72 | TB5002 | 6 | E | | C01239 | =B | D | | 115-199 |
| 0201 | 16 | GA | | 6-0 | 24-51-21 | TB5004 | 8 | E | | C04185 | =B | D | | 001-099 |
| 0201 | 16 | GA | | 5-0 | 24-51-21 | TB5004 | 8 | E | | C04185 | =B | D | | 115-199 |
| 0203 | 16 | GA | | 3-0 | 24-51-21 | C04253 | =B | D | | C01277 | =B | D | * | 115-199 |
| 0204 | 16 | GA | | 4-0 | 24-51-21 | C01432 | =B | D | | C01277 | =B | D | * | ALL |
| 0206 | 16 | GA | | 5-0 | 24-51-21 | TB5004 | 7 | E | | C04208 | =B | D | * | ALL |
| 0208 | 16 | GA | | 3-0 | 24-51-21 | C04357 | =B | D | * | C04186 | =B | D | * | ALL |
| 0209 | 16 | GA | | 4-0 | 24-51-21 | C04079 | =B | D | | C01250 | =B | D | * | ALL |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|--|---------|----------|--------|-------|------|------|--------|--------|------|-------------|---------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W0116 | 286N0116 | | | P11-4 MODULE WIRING - RIGHT BUSSES (continued) | | | | | | | | | | | | |
| 0210 | 16 | GA | | | 2-0 | 24-51-21 | C04186 | =B | D | * | C01250 | =B | D | * | 001-099 | |
| 0210 | 16 | GA | | | 2-0 | 24-51-21 | C01250 | =B | D | * | C04186 | =B | D | * | 115-199 | |
| 0212 | 16 | GA | | | 5-0 | 24-51-21 | TB5004 | | 6 | E | | C01336 | =B | D | * | ALL |
| 0213 | 16 | GA | | | 3-0 | 24-51-21 | C01336 | =B | D | * | C01240 | =B | D | * | 001-099 | |
| 0213 | 16 | GA | | | 3-0 | 24-51-21 | C01336 | =B | D | * | C01240 | =B | D | | 115-199 | |
| 0214 | 16 | GA | | | 4-0 | 24-51-21 | C01240 | =B | D | * | C04082 | =B | D | | 001-099 | |
| 0214 | 16 | GA | | | 1-0 | 24-51-21 | C01240 | =B | D | | C01248 | =B | D | * | 115-199 | |
| 0215 | 16 | GA | | | 4-0 | 24-51-21 | C01248 | =B | D | * | C04082 | =B | D | | 115-199 | |
| 0301 | 12 | HA | | | 6-0 | 24-51-52 | TB5004 | | 11 | E | | C04192 | =B | D | * | 001-099 |
| 0301 | 12 | HA | | | 5-5 | 24-51-52 | TB5004 | | 11 | E | | C04192 | =B | D | * | 115-199 |
| 0302 | 12 | HA | | | 3-0 | 24-51-52 | C04192 | =B | D | * | C01225 | =B | D | | 001-099 | |
| 0302 | 12 | HA | | | 2-5 | 24-51-52 | C04192 | =B | D | * | C01225 | =B | D | | 115-199 | |
| 0303 | 12 | HA | | | 6-0 | 24-51-52 | TB5004 | | 10 | E | | C01294 | =B | D | | 001-099 |
| 0303 | 12 | HA | | | 5-0 | 24-51-52 | TB5004 | | 10 | E | | C01294 | =B | D | | 115-199 |
| 0305 | 12 | HA | | | 3-0 | 24-51-52 | C01314 | =B | D | * | C01101 | =B | D | | 001-099 | |
| 0305 | 12 | HA | | | 2-6 | 24-51-52 | C01314 | =B | D | * | C01101 | =B | D | | 115-199 | |
| 0308 | 12 | HA | | | 6-0 | 24-51-52 | TB5004 | | 9 | E | | C04193 | =B | D | | 001-099 |
| 0308 | 12 | HA | | | 5-0 | 24-51-52 | TB5004 | | 9 | E | | C04193 | =B | D | | 115-199 |
| 0315 | 12 | HA | | | 4-0 | 24-51-52 | C01314 | =B | D | * | C00794 | =B | D | | 001-099 | |
| 0315 | 12 | HA | | | 3-4 | 24-51-52 | C01314 | =B | D | * | C00794 | =B | D | | 115-199 | |
| 0401 | 12 | HA | | | 5-0 | 24-51-23 | TB5004 | | 1 | E | | C03011 | A2 | D | | 001-099 |
| 0401 | 12 | HA | | | 4-2 | 24-51-23 | TB5004 | | 1 | E | | C03011 | A2 | D | | 115-199 |
| 0402 | 12 | HA | | | 5-0 | 24-51-23 | TB5004 | | 2 | E | | C03011 | B2 | D | | 001-099 |
| 0402 | 12 | HA | | | 4-2 | 24-51-23 | TB5004 | | 2 | E | | C03011 | B2 | D | | 115-199 |
| 0403 | 12 | HA | | | 5-0 | 24-51-23 | TB5004 | | 3 | E | | C03011 | C2 | D | | 001-099 |
| 0403 | 12 | HA | | | 4-2 | 24-51-23 | TB5004 | | 3 | E | | C03011 | C2 | D | | 115-199 |
| 0404 | 08 | HA | | | 1-1 | 24-54-21 | C04235 | =B | D | | C01284 | =B | D | | 115-199 | |
| 0501 | 10 | HA | | | 6-0 | 24-54-21 | TB5004 | | 4 | E | | C01284 | =B | D | | 001-099 |
| 0501 | 12 | HA | | | 4-10 | 24-54-21 | TB5004 | | 4 | E | | C01284 | =B | D | * | 115-199 |
| 0502 | 12 | HA | | | 4-0 | 24-54-21 | C01284 | =B | D | * | C00574 | =B | D | * | 001-099 | |
| 0502 | 12 | HA | | | 3-11 | 24-54-21 | C01284 | =B | D | * | C00574 | =B | D | * | 115-199 | |
| 0503 | 12 | HA | | | 2-0 | 24-54-21 | C00763 | =B | D | | C00574 | =B | D | * | 001-099 | |
| 0503 | 12 | HA | | | 2-0 | 24-54-21 | C04209 | =B | D | | C00574 | =B | D | * | 115-199 | |
| 0504 | 12 | HA | | | 2-0 | 24-54-21 | C01284 | =B | D | * | C04261 | =B | D | | 001-099 | |
| 0504 | 12 | HA | | | 1-1 | 24-54-21 | C01284 | =B | D | * | C04261 | =B | D | | 115-199 | |
| 0506 | 12 | HA | | | 2-11 | 24-54-21 | C00574 | =B | D | | C04680 | =B | D | | ALL | |
| 0623 | 16 | GA | | | 3-0 | 24-51-21 | C04357 | =B | D | * | C04208 | =B | D | * | ALL | |
| 0633 | 14 | GA | | | 4-0 | 24-53-21 | C04183 | =B | D | * | C01287 | =B | D | * | 115-199 | |
| 0643 | 16 | GA | | | 4-0 | 24-54-21 | C01302 | =B | D | | C04225 | =B | D | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0116 | 286N0116 | | | P11-4 MODULE WIRING - RIGHT BUSESSES (continued) | | | | | | | | | | | |
| 0683 | 16 | | GA | | 2-0 | 24-51-21 | C04184 | =B | D | | C01277 | =B | D | * | 001-099 |
| ZZAA | 05 | | ZB | | 0-0 | 24-54-21 | C01170 | =B | D | | C04279 | =B | D | | ALL |
| ZZAB | 02 | | ZB | | 0-0 | 24-54-21 | C01355 | =B | D | | C01320 | =B | D | | ALL |
| ZZAF | 04 | | ZB | | 0-0 | 24-54-21 | C00825 | =B | D | | C04144 | =B | D | | ALL |
| ZZAG | 04 | | ZB | | 0-0 | 24-54-21 | C04029 | =B | D | | C01273 | =B | D | | ALL |
| ZZAI | 02 | | ZB | | 0-0 | 24-54-21 | C04127 | =B | D | | C04130 | =B | D | | 115-199 |
| ZZAJ | 02 | | ZB | | 0-0 | 24-54-21 | C01302 | =B | D | | C01280 | =B | D | | ALL |
| ZZAK | 04 | | ZB | | 0-0 | 24-54-21 | C00766 | =B | D | | C00764 | =B | D | | ALL |
| ZZAL | 02 | | ZB | | 0-0 | 24-54-21 | C01342 | =B | D | | C01333 | =B | D | | 001-099 |
| ZZAM | 04 | | ZB | | 0-0 | 24-54-21 | C04292 | =B | D | | C04045 | =B | D | | ALL |
| ZZAN | 02 | | ZB | | 0-0 | 24-54-21 | C04471 | =B | D | | C04470 | =B | D | | 001-002, 115-199 |
| ZZAN | 02 | | ZB | | 0-0 | 24-54-21 | C04470 | =B | D | | C04471 | =B | D | | 003-099 |
| ZZAP | 03 | | ZB | | 0-0 | 24-54-21 | C04127 | =B | D | | C04108 | =B | D | | 001-099 |
| ZZAR | 00 | | ZB | | 0-0 | 24-54-21 | C04108 | =B | D | | C04130 | =B | D | | 001-099 |
| ZZAW | 02 | | ZB | | 0-0 | 24-51-22 | C00565 | =B | D | | C04459 | =B | D | | 001-099 |
| ZZBA | 02 | | ZB | | 0-0 | 24-53-21 | C01251 | =B | D | | C01281 | =B | D | | ALL |
| ZZBB | 02 | | ZB | | 0-0 | 24-53-21 | C04102 | =B | D | | C04100 | =B | D | | ALL |
| ZZBC | 02 | | ZB | | 0-0 | 24-54-21 | C04309 | =B | D | | C04131 | =B | D | | 115-199 |
| ZZCA | 02 | | ZB | | 0-0 | 24-51-21 | C04184 | =B | D | | C04185 | =B | D | | ALL |
| ZZCB | 03 | | ZB | | 0-0 | 24-51-21 | C04020 | =B | D | | C04253 | =B | D | | 115-199 |
| ZZCC | 00 | | ZB | | 0-0 | 24-51-21 | C04020 | =B | D | | C04021 | =B | D | | 115-199 |
| ZZCD | 00 | | ZB | | 0-0 | 24-51-21 | C04021 | =B | D | | C04253 | =B | D | | 115-199 |
| ZZEE | 02 | | ZB | | 0-0 | 24-51-52 | C01225 | =B | D | | C01227 | =B | D | | ALL |
| ZZOA | 00 | | ZB | | 0-0 | 24-54-21 | C04292 | =B | D | | C04026 | =B | D | | ALL |
| ZZOC | 00 | | ZB | | 0-0 | 24-54-21 | C01172 | =B | D | | C01173 | =B | D | | 001-099 |
| ZZOC | 00 | | ZB | | 0-0 | 24-54-21 | C04279 | =B | D | | C01172 | =B | D | | 115-199 |
| ZZOD | 00 | | ZB | | 0-0 | 24-54-21 | C01173 | =B | D | | C01174 | =B | D | | 001-099 |
| ZZOD | 00 | | ZB | | 0-0 | 24-54-21 | C01173 | =B | D | | C01172 | =B | D | | 115-199 |
| ZZOE | 00 | | ZB | | 0-0 | 24-54-21 | C01174 | =B | D | | C01170 | =B | D | | 001-099 |
| ZZOE | 00 | | ZB | | 0-0 | 24-54-21 | C01173 | =B | D | | C01174 | =B | D | | 115-199 |
| ZZOF | 00 | | ZB | | 0-0 | 24-54-21 | C04144 | =B | D | | C00803 | =B | D | | 001-099 |
| ZZOF | 00 | | ZB | | 0-0 | 24-54-21 | C01170 | =B | D | | C01174 | =B | D | | 115-199 |
| ZZOG | 00 | | ZB | | 0-0 | 24-54-21 | C00803 | =B | D | | C00823 | =B | D | | 001-099 |
| ZZOG | 00 | | ZB | | 0-0 | 24-54-21 | C04144 | =B | D | | C00803 | =B | D | | 115-199 |
| ZZOH | 00 | | ZB | | 0-0 | 24-54-21 | C00823 | =B | D | | C00825 | =B | D | | 001-099 |
| ZZOH | 00 | | ZB | | 0-0 | 24-54-21 | C00823 | =B | D | | C00803 | =B | D | | 115-199 |
| ZZOI | 02 | | ZB | | 0-0 | 24-54-21 | C04131 | =B | D | | C04309 | =B | D | | 001-099 |
| ZZOI | 00 | | ZB | | 0-0 | 24-54-21 | C00823 | =B | D | | C00825 | =B | D | | 115-199 |
| ZZOL | 02 | | ZB | | 0-0 | 24-54-21 | C01144 | =B | D | | C01145 | =B | D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0116 | 286N0116 | | | P11-4 MODULE WIRING - RIGHT BUSESSES (continued) | | | | | | | | | | | |
| ZZOM | 00 | | ZB | | 0-0 | 24-54-21 | C01273 | =B | D | | C04031 | =B | D | | 115-199 |
| ZZON | 00 | | ZB | | 0-0 | 24-54-21 | C04030 | =B | D | | C04031 | =B | D | | 115-199 |
| ZZOP | 00 | | ZB | | 0-0 | 24-54-21 | C04030 | =B | D | | C04029 | =B | D | | 115-199 |
| ZZOQ | 00 | | ZB | | 0-0 | 24-54-21 | C04045 | =B | D | | C04014 | =B | D | | 001-099 |
| ZZOR | 00 | | ZB | | 0-0 | 24-54-21 | C04014 | =B | D | | C04026 | =B | D | | 001-099 |
| ZZOS | 00 | | ZB | | 0-0 | 24-54-21 | C04279 | =B | D | | C01172 | =B | D | | 001-099 |
| ZZOT | 00 | | ZB | | 0-0 | 24-54-21 | C01273 | =B | D | | C04031 | =B | D | | 001-099 |
| ZZOT | 00 | | ZB | | 0-0 | 24-54-21 | C04045 | =B | D | | C04014 | =B | D | | 115-199 |
| ZZOU | 00 | | ZB | | 0-0 | 24-54-21 | C04030 | =B | D | | C04029 | =B | D | | 001-099 |
| ZZOV | 00 | | ZB | | 0-0 | 24-54-21 | C04031 | =B | D | | C04030 | =B | D | | 001-099 |
| ZZOV | 00 | | ZB | | 0-0 | 24-54-21 | C04026 | =B | D | | C04014 | =B | D | | 115-199 |
| ZZOW | 02 | | ZB | | 0-0 | 24-54-21 | C00795 | =B | D | | C00740 | =B | D | | 001-099 |
| ZZOY | 00 | | ZB | | 0-0 | 24-54-21 | C00766 | =B | D | | C00765 | =B | D | | ALL |
| ZZOZ | 00 | | ZB | | 0-0 | 24-54-21 | C00765 | =B | D | | C00763 | =B | D | | ALL |
| ZZPA | 00 | | ZB | | 0-0 | 24-54-21 | C00763 | =B | D | | C00764 | =B | D | | ALL |
| ZZPD | 00 | | ZB | | 0-0 | 24-54-21 | C04130 | =B | D | | C04127 | =B | D | | 001-099 |
| ZZXA | 02 | | ZA | | 0-0 | 24-54-21 | C04127 | =B | D | | C04189 | =B | D | | 115-199 |
| ZZXB | 02 | | ZA | | 0-0 | 24-54-21 | C04197 | =B | D | | C04031 | =B | D | | ALL |
| ZZXC | 02 | | ZA | | 0-0 | 24-54-21 | C04072 | =B | D | | C01053 | =B | D | | ALL |
| ZZXD | 02 | | ZA | | 0-0 | 24-51-21 | C04082 | =B | D | | C04094 | =B | D | | ALL |
| ZZXE | 02 | | ZA | | 0-0 | 24-54-21 | C04131 | =B | D | | C04195 | =B | D | | 001-099 |
| ZZXF | 02 | | ZA | | 0-0 | 24-54-21 | C00803 | =B | D | | C04225 | =B | D | | ALL |
| ZZXH | 02 | | ZA | | 0-0 | 24-51-21 | C04184 | =B | D | | C04020 | =B | D | | 115-199 |
| ZZXX | 02 | | ZA | | 0-0 | 24-54-21 | C04223 | =B | D | | C00741 | =B | D | | 115-199 |
| ZZYB | 02 | | ZA | | 0-0 | 24-54-21 | C04470 | =B | D | | C04189 | =B | D | | ALL |
| ZZYC | 02 | | ZA | | 0-0 | 24-54-21 | C04130 | =B | D | | C04471 | =B | D | | 003-099 |
| ZZYC | 02 | | ZA | | 0-0 | 24-54-21 | C04108 | =B | D | | C04189 | =B | D | | 115-199 |
| ZZYD | 02 | | ZA | | 0-0 | 24-54-21 | C04130 | =B | D | | C01202 | =B | D | | 001-099 |
| ZZYI | 02 | | ZA | | 0-0 | 24-54-21 | C01202 | =B | D | | C04072 | =B | D | | 001-099 |
| ZZYK | 02 | | ZA | | 0-0 | 24-54-21 | C00661 | =B | D | | C04072 | =B | D | | ALL |
| ZZYL | 02 | | ZA | | 0-0 | 24-51-25 | C04036 | =B | D | | C00701 | =B | D | | ALL |
| ZZYO | 02 | | ZA | | 0-0 | 24-54-21 | C04030 | =B | D | | C01342 | =B | D | | ALL |
| ZZYP | 02 | | ZA | | 0-0 | 24-54-21 | C00661 | =B | D | | C01333 | =B | D | | ALL |
| ZZYQ | 02 | | ZA | | 0-0 | 24-54-21 | C01145 | =B | D | | C01340 | =B | D | | ALL |
| ZZYR | 02 | | ZA | | 0-0 | 24-54-21 | C01342 | =B | D | | C01333 | =B | D | | 115-199 |
| ZZYS | 02 | | ZA | | 0-0 | 24-54-21 | C04131 | =B | D | | C04197 | =B | D | | ALL |
| ZZYT | 02 | | ZA | | 0-0 | 24-51-52 | C01314 | =B | D | | C01294 | =B | D | | ALL |
| ZZYV | 02 | | ZA | | 0-0 | 24-54-21 | C04131 | =B | D | | C04195 | =B | D | | 115-199 |
| ZZYX | 02 | | ZA | | 0-0 | 24-53-21 | C01281 | =B | D | | C01287 | =B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0116 | 286N0116 | | | P11-4 MODULE WIRING - RIGHT BUSESSES (continued) | | | | | | | | | | | |
| ZZYY | 02 | | ZA | | 0-0 | 24-54-21 | C04144 | =B | D | | C00740 | =B | D | | 001-099 |
| ZZYY | 02 | | ZA | | 0-0 | 24-54-21 | C04144 | =B | D | | C00741 | =B | D | | 115-199 |
| ZZYZ | 02 | | ZA | | 0-0 | 24-54-21 | C00823 | =B | D | | C01320 | =B | D | | ALL |
| ZZZA | 02 | | ZA | | 0-0 | 24-54-21 | C00825 | =B | D | | C04195 | =B | D | | ALL |
| ZZZB | 02 | | ZA | | 0-0 | 24-54-21 | C04131 | =B | D | | C01144 | =B | D | | 001-099 |
| ZZZB | 02 | | ZA | | 0-0 | 24-54-21 | C04309 | =B | D | | C01144 | =B | D | | 115-199 |
| ZZZD | 02 | | ZA | | 0-0 | 24-51-23 | C03012 | | C2 | D | C03011 | | C2 | D | ALL |
| ZZZE | 02 | | ZA | | 0-0 | 24-51-23 | C03012 | | B2 | D | C03011 | | B2 | D | ALL |
| ZZZF | 02 | | ZA | | 0-0 | 24-51-23 | C03012 | | A2 | D | C03011 | | A2 | D | ALL |
| ZZZG | 02 | | ZA | | 0-0 | 24-54-21 | C00795 | =B | D | | C04223 | =B | D | | ALL |
| ZZZH | 02 | | ZA | | 0-0 | 24-54-21 | C01053 | =B | D | | C04292 | =B | D | | 001-099 |
| W0118 | 286N0118 | | | P11-1 MODULE WIRING - STANDBY BUSESSES | | | | | | | | | | | |
| 0001 | 12 | | HA | | 5-9 | 24-54-73 | TB5005 | | 1 | E | C00826 | =B | D | | 115-199 |
| 0014 | 16 | | GA | | 7-0 | 24-54-73 | TB5005 | | 2 | E | C01437 | =B | D | | 115-199 |
| 0027 | 12 | | HA | | 1-5 | 24-54-73 | C00604 | =B | D | | C01560 | =B | D | | 115-199 |
| 0030 | 16 | | GA | | 3-0 | 24-54-73 | C04205 | =B | D | | C00566 | =B | D | | 115-199 |
| 0038 | 16 | | GA | | 2-0 | 24-54-73 | C01521 | =B | D | | C01438 | =B | D | | 115-199 |
| 0602 | 16 | | GA | | 3-0 | 24-54-73 | C00625 | =B | D | | C01537 | =B | D | | 115-199 |
| ZZAB | 05 | | ZB | | 0-0 | 24-54-73 | C01533 | =B | D | | C01529 | =B | D | | 115-199 |
| ZZAC | 02 | | ZB | | 0-0 | 24-54-73 | C00591 | =B | D | | C00604 | =B | D | | 115-199 |
| ZZAD | 02 | | ZB | | 0-0 | 24-54-73 | C00521 | =B | D | | C01560 | =B | D | | 115-199 |
| ZZAF | 02 | | ZB | | 0-0 | 24-54-73 | C00619 | =B | D | | C04239 | =B | D | | 115-199 |
| ZZAG | 03 | | ZB | | 0-0 | 24-54-73 | C00826 | =B | D | | C01120 | =B | D | | 115-199 |
| ZZAH | 03 | | ZB | | 0-0 | 24-54-73 | C00702 | =B | D | | C04039 | =B | D | | 115-199 |
| ZZAJ | 02 | | ZB | | 0-0 | 24-54-73 | C01480 | =B | D | | C01482 | =B | D | | 115-199 |
| ZZAK | 00 | | ZB | | 0-0 | 24-54-73 | C00606 | =B | D | | C04118 | =B | D | | 115-199 |
| ZZBA | 04 | | ZB | | 0-0 | 24-54-73 | C01434 | =B | D | | C01438 | =B | D | | 115-199 |
| ZZBB | 03 | | ZB | | 0-0 | 24-54-73 | C00595 | =B | D | | C04118 | =B | D | | 115-199 |
| ZZBC | 02 | | ZB | | 0-0 | 24-54-73 | C01283 | =B | D | | C01246 | =B | D | | 115-199 |
| ZZBD | 02 | | ZB | | 0-0 | 24-54-73 | C04206 | =B | D | | C04205 | =B | D | | 115-199 |
| ZZBE | 00 | | ZB | | 0-0 | 24-54-73 | C00595 | =B | D | | C00606 | =B | D | | 115-199 |
| ZZDC | 02 | | ZB | | 0-0 | 24-54-73 | C04665 | =B | D | | C04664 | =B | D | | 115-199 |
| ZZHE | 04 | | ZB | | 0-0 | 24-54-73 | C00573 | =B | D | | C00683 | =B | D | | 115-199 |
| ZZOA | 00 | | ZB | | 0-0 | 24-54-73 | C01438 | =B | D | | C01437 | =B | D | | 115-199 |
| ZZOB | 00 | | ZB | | 0-0 | 24-54-73 | C01435 | =B | D | | C01437 | =B | D | | 115-199 |
| ZZOC | 00 | | ZB | | 0-0 | 24-54-73 | C01435 | =B | D | | C01434 | =B | D | | 115-199 |
| ZZOD | 00 | | ZB | | 0-0 | 24-54-73 | C00567 | =B | D | | C00658 | =B | D | | 115-199 |
| ZZOE | 00 | | ZB | | 0-0 | 24-54-73 | C00683 | =B | D | | C00658 | =B | D | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|--------|------|-------------|--------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W0118 | 286N0118 | | | | P11-1 MODULE WIRING - STANDBY BUSSES (continued) | | | | | | | | | | | |
| ZZOF | 00 | | ZB | | 0-0 | 24-54-73 | C00826 | =B | D | | | C04194 | =B | D | | 115-199 |
| ZZOG | 00 | | ZB | | 0-0 | 24-54-73 | C04194 | =B | D | | | C01120 | =B | D | | 115-199 |
| ZZOH | 00 | | ZB | | 0-0 | 24-54-73 | C01529 | =B | D | | | C01528 | =B | D | | 115-199 |
| ZZOJ | 00 | | ZB | | 0-0 | 24-54-73 | C01528 | =B | D | | | C01039 | =B | D | | 115-199 |
| ZZOK | 00 | | ZB | | 0-0 | 24-54-73 | C00573 | =B | D | | | C00567 | =B | D | | 115-199 |
| ZZOL | 00 | | ZB | | 0-0 | 24-54-73 | C00702 | =B | D | | | C00653 | =B | D | | 115-199 |
| ZZOM | 00 | | ZB | | 0-0 | 24-54-73 | C00653 | =B | D | | | C04039 | =B | D | | 115-199 |
| ZZON | 00 | | ZB | | 0-0 | 24-54-73 | C01039 | =B | D | | | C01033 | =B | D | | 115-199 |
| ZZOP | 00 | | ZB | | 0-0 | 24-54-73 | C01033 | =B | D | | | C01533 | =B | D | | 115-199 |
| ZZOR | 00 | | ZB | | 0-0 | 24-54-73 | C00619 | =B | D | | | C04239 | =B | D | | 115-199 |
| ZZOS | 02 | | ZB | | 0-0 | 24-54-73 | C00544 | =B | D | | | C00622 | =B | D | | 115-199 |
| ZZXB | 02 | | ZA | | 0-0 | 24-54-73 | C00770 | =B | D | | | C04206 | =B | D | | 115-199 |
| ZZXC | 02 | | ZA | | 0-0 | 24-54-73 | C00595 | =B | D | | | C01337 | =B | D | | 115-199 |
| ZZXD | 02 | | ZA | | 0-0 | 24-54-73 | C00544 | =B | D | | | C01338 | =B | D | | 115-199 |
| ZZXG | 02 | | ZA | | 0-0 | 24-54-73 | C00573 | =B | D | | | C04110 | =B | D | | 115-199 |
| ZZYC | 02 | | ZA | | 0-3 | 24-54-73 | C01039 | =B | D | | | C01480 | =B | D | | 115-199 |
| ZZYD | 02 | | ZA | | 0-3 | 24-54-73 | C01533 | =B | D | | | C01534 | =B | D | | 115-199 |
| ZZYE | 02 | | ZA | | 0-0 | 24-54-73 | C00544 | =B | D | | | C00619 | =B | D | | 115-199 |
| ZZYG | 02 | | ZA | | 0-0 | 24-54-73 | C01528 | =B | D | | | C01541 | =B | D | | 115-199 |
| ZZYJ | 02 | | ZA | | 0-0 | 24-54-73 | C00683 | =B | D | | | C01529 | =B | D | | 115-199 |
| ZZYM | 02 | | ZA | | 0-0 | 24-54-73 | C00619 | =B | D | | | C04665 | =B | D | | 115-199 |
| ZZZA | 02 | | ZA | | 0-3 | 24-54-73 | C01435 | =B | D | | | C01537 | =B | D | | 115-199 |
| ZZZB | 02 | | ZA | | 0-3 | 24-54-73 | C01434 | =B | D | | | C01538 | =B | D | | 115-199 |
| ZZZC | 02 | | ZA | | 0-0 | 24-54-73 | C01538 | =B | D | | | C01246 | =B | D | | 115-199 |
| ZZZE | 02 | | ZA | | 0-0 | 24-54-73 | C04259 | =B | D | | | C01283 | =B | D | | 115-199 |
| ZZZF | 02 | | ZA | | 0-0 | 24-54-73 | C04259 | =B | D | | | C04602 | =B | D | | 115-199 |
| ZZZG | 02 | | ZA | | 0-0 | 24-54-73 | C00521 | =B | D | | | C00658 | =B | D | | 115-199 |
| ZZZI | 02 | | ZA | | 0-0 | 24-54-73 | C00625 | =B | D | | | C04206 | =B | D | | 115-199 |
| ZZZJ | 02 | | ZA | | 0-0 | 24-54-73 | C00591 | =B | D | | | C00619 | =B | D | | 115-199 |
| ZZZL | 02 | | ZA | | 0-0 | 24-54-73 | C00567 | =B | D | | | C04039 | =B | D | | 115-199 |
| ZZZP | 02 | | ZA | | 0-0 | 24-54-73 | C01534 | =B | D | | | C00826 | =B | D | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0110

Page 18 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0120 | 286N0120 | | | P11-2 MODULE WIRING - BATTERY BUSES | | | | | | | | | | | |
| 0001 | 08 | | HA | | 7-0 | 24-54-71 | TB5006 | | 4 | E | C01051 | =B | D | | 115-199 |
| 0014 | 18 | | GA | | 3-0 | 24-54-71 | C01481 | | =B | D | C04478 | =B | D | | 115-199 |
| 0101 | 16 | | GA | | 3-0 | 24-54-71 | C01307 | | =B | D | C00788 | =B | D | | 115-199 |
| 0102 | 12 | | HA | | 2-0 | 24-54-71 | C04216 | | =B | D | C04151 | =B | D | | 115-199 |
| ZZAA | 11 | | ZB | | 0-0 | 24-54-71 | C04061 | | =B | D | C01051 | =B | D | | 115-199 |
| ZZAD | 12 | | ZB | | 0-0 | 24-54-71 | C01310 | | =B | D | C04255 | =B | D | | 115-199 |
| ZZAG | 09 | | ZB | | 0-0 | 24-54-71 | C01010 | | =B | D | C00788 | =B | D | | 115-199 |
| ZZAJ | 04 | | ZB | | 0-0 | 24-54-71 | C01322 | | =B | D | C04037 | =B | D | | 115-199 |
| ZZAK | 08 | | ZB | | 0-0 | 24-54-71 | C00703 | | =B | D | C01306 | =B | D | | 115-199 |
| ZZAM | 07 | | ZB | | 0-0 | 24-54-71 | C04290 | | =B | D | C01481 | =B | D | | 115-199 |
| ZZAN | 07 | | ZB | | 0-0 | 24-54-71 | C04281 | | =B | D | C01510 | =B | D | | 115-199 |
| ZZBA | 00 | | ZB | | 0-0 | 24-54-71 | C00796 | | =B | D | C04252 | =B | D | | 115-199 |
| ZZBB | 00 | | ZB | | 0-0 | 24-54-71 | C04251 | | =B | D | C04252 | =B | D | | 115-199 |
| ZZBC | 00 | | ZB | | 0-0 | 24-54-71 | C04132 | | =B | D | C04133 | =B | D | | 115-199 |
| ZZBD | 00 | | ZB | | 0-0 | 24-54-71 | C04133 | | =B | D | C04175 | =B | D | | 115-199 |
| ZZBE | 00 | | ZB | | 0-0 | 24-54-71 | C04175 | | =B | D | C04054 | =B | D | | 115-199 |
| ZZBF | 00 | | ZB | | 0-0 | 24-54-71 | C00703 | | =B | D | C00704 | =B | D | | 115-199 |
| ZZBG | 00 | | ZB | | 0-0 | 24-54-71 | C00704 | | =B | D | C01214 | =B | D | | 115-199 |
| ZZBH | 00 | | ZB | | 0-0 | 24-54-71 | C04025 | | =B | D | C04023 | =B | D | | 115-199 |
| ZZBJ | 00 | | ZB | | 0-0 | 24-54-71 | C04054 | | =B | D | C04025 | =B | D | | 115-199 |
| ZZBL | 00 | | ZB | | 0-0 | 24-54-71 | C01481 | | =B | D | C01483 | =B | D | | 115-199 |
| ZZBM | 00 | | ZB | | 0-0 | 24-54-71 | C01483 | | =B | D | C04251 | =B | D | | 115-199 |
| ZZBN | 00 | | ZB | | 0-0 | 24-54-71 | C04151 | | =B | D | C04114 | =B | D | | 115-199 |
| ZZBP | 00 | | ZB | | 0-0 | 24-54-71 | C04114 | | =B | D | C04113 | =B | D | | 115-199 |
| ZZBR | 00 | | ZB | | 0-0 | 24-54-71 | C04281 | | =B | D | C04152 | =B | D | | 115-199 |
| ZZCD | 00 | | ZB | | 0-0 | 24-54-71 | C04037 | | =B | D | C01325 | =B | D | | 115-199 |
| ZZDA | 00 | | ZB | | 0-0 | 24-54-71 | C01303 | | =B | D | C01048 | =B | D | | 115-199 |
| ZZDB | 00 | | ZB | | 0-0 | 24-54-71 | C01303 | | =B | D | C01310 | =B | D | | 115-199 |
| ZZDD | 00 | | ZB | | 0-0 | 24-54-71 | C00772 | | =B | D | C00788 | =B | D | | 115-199 |
| ZZDE | 00 | | ZB | | 0-0 | 24-54-71 | C00784 | | =B | D | C00776 | =B | D | | 115-199 |
| ZZDF | 00 | | ZB | | 0-0 | 24-54-71 | C00776 | | =B | D | C00785 | =B | D | | 115-199 |
| ZZDG | 00 | | ZB | | 0-0 | 24-54-71 | C00785 | | =B | D | C00772 | =B | D | | 115-199 |
| ZZDH | 04 | | ZB | | 0-0 | 24-54-71 | C04085 | | =B | D | C00551 | =B | D | | 115-199 |
| ZZDJ | 00 | | ZB | | 0-0 | 24-54-71 | C04085 | | =B | D | C01121 | =B | D | | 115-199 |
| ZZDK | 00 | | ZB | | 0-0 | 24-54-71 | C01121 | | =B | D | C00548 | =B | D | | 115-199 |
| ZZEA | 00 | | ZB | | 0-0 | 24-54-71 | C01308 | | =B | D | C01201 | =B | D | | 115-199 |
| ZZEB | 00 | | ZB | | 0-0 | 24-54-71 | C01201 | | =B | D | C01200 | =B | D | | 115-199 |
| ZZEC | 00 | | ZB | | 0-0 | 24-54-71 | C01200 | | =B | D | C01307 | =B | D | | 115-199 |
| ZZHA | 00 | | ZB | | 0-0 | 24-54-71 | C01148 | | =B | D | C01147 | =B | D | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0120 | 286N0120 | | | P11-2 MODULE WIRING - BATTERY BUSSES (continued) | | | | | | | | | | | |
| ZZOA | 00 | | ZB | | 0-0 | 24-54-71 | C01051 | =B | D | | C01052 | =B | D | | 115-199 |
| ZZOB | 00 | | ZB | | 0-0 | 24-54-71 | C04132 | =B | D | | C01052 | =B | D | | 115-199 |
| ZZOC | 00 | | ZB | | 0-0 | 24-54-71 | C04023 | =B | D | | C04216 | =B | D | | 115-199 |
| ZZOD | 00 | | ZB | | 0-0 | 24-54-71 | C04061 | =B | D | | C04216 | =B | D | | 115-199 |
| ZZOE | 00 | | ZB | | 0-0 | 24-54-71 | C04152 | =B | D | | C04151 | =B | D | | 115-199 |
| ZZOF | 00 | | ZB | | 0-0 | 24-54-71 | C04113 | =B | D | | C01511 | =B | D | | 115-199 |
| ZZOG | 00 | | ZB | | 0-0 | 24-54-71 | C01510 | =B | D | | C01511 | =B | D | | 115-199 |
| ZZOI | 00 | | ZB | | 0-0 | 24-54-71 | C04257 | =B | D | | C01147 | =B | D | | 115-199 |
| ZZOJ | 00 | | ZB | | 0-0 | 24-54-71 | C01048 | =B | D | | C01058 | =B | D | | 115-199 |
| ZZOK | 00 | | ZB | | 0-0 | 24-54-71 | C01184 | =B | D | | C01058 | =B | D | | 115-199 |
| ZZOL | 00 | | ZB | | 0-0 | 24-54-71 | C01184 | =B | D | | C01183 | =B | D | | 115-199 |
| ZZOM | 00 | | ZB | | 0-0 | 24-54-71 | C01175 | =B | D | | C01183 | =B | D | | 115-199 |
| ZZOO | 00 | | ZB | | 0-0 | 24-54-71 | C00784 | =B | D | | C00775 | =B | D | | 115-199 |
| ZZOP | 00 | | ZB | | 0-0 | 24-54-71 | C00783 | =B | D | | C00775 | =B | D | | 115-199 |
| ZZOQ | 00 | | ZB | | 0-0 | 24-54-71 | C00783 | =B | D | | C00774 | =B | D | | 115-199 |
| ZZOR | 00 | | ZB | | 0-0 | 24-54-71 | C01010 | =B | D | | C00774 | =B | D | | 115-199 |
| ZZOS | 00 | | ZB | | 0-0 | 24-54-71 | C04257 | =B | D | | C04255 | =B | D | | 115-199 |
| ZZOT | 00 | | ZB | | 0-0 | 24-54-71 | C01325 | =B | D | | C01323 | =B | D | | 115-199 |
| ZZOU | 00 | | ZB | | 0-0 | 24-54-71 | C01306 | =B | D | | C01308 | =B | D | | 115-199 |
| ZZOV | 00 | | ZB | | 0-0 | 24-54-71 | C01307 | =B | D | | C01214 | =B | D | | 115-199 |
| ZZOW | 00 | | ZB | | 0-0 | 24-54-71 | C01322 | =B | D | | C01323 | =B | D | | 115-199 |
| ZZOX | 00 | | ZB | | 0-0 | 24-54-71 | C01175 | =B | D | | C01132 | =B | D | | 115-199 |
| ZZOY | 00 | | ZB | | 0-0 | 24-54-71 | C01132 | =B | D | | C01148 | =B | D | | 115-199 |
| ZZOZ | 00 | | ZB | | 0-0 | 24-54-71 | C00796 | =B | D | | C01390 | =B | D | | 115-199 |
| ZZPA | 00 | | ZB | | 0-0 | 24-54-71 | C04290 | =B | D | | C01390 | =B | D | | 115-199 |
| ZZPB | 00 | | ZB | | 0-0 | 24-54-71 | C00551 | =B | D | | C00548 | =B | D | | 115-199 |
| ZZXC | 02 | | ZA | | 0-0 | 24-54-71 | C01321 | =B | D | | C00783 | =B | D | | 115-199 |
| ZZXD | 02 | | ZA | | 0-0 | 24-54-71 | C01308 | =B | D | | C01390 | =B | D | | 115-199 |
| ZZXE | 02 | | ZA | | 0-0 | 24-54-71 | C00551 | =B | D | | C00784 | =B | D | | 115-199 |
| ZZXF | 02 | | ZA | | 0-0 | 24-54-71 | C04257 | =B | D | | C04023 | =B | D | | 115-199 |
| ZZXG | 02 | | ZA | | 0-0 | 24-54-71 | C01184 | =B | D | | C04132 | =B | D | | 115-199 |
| ZZYB | 02 | | ZA | | 0-0 | 24-54-71 | C01323 | =B | D | | C00775 | =B | D | | 115-199 |
| ZZYH | 02 | | ZA | | 0-0 | 24-54-71 | C01511 | =B | D | | C04085 | =B | D | | 115-199 |
| W0122 | 286N0122 | | | P11-2 MODULE WIRING - CENTER BUSSES | | | | | | | | | | | |
| 0001 | 18 | | GA | | 6-0 | 24-51-31 | C00524 | =B | D | | TB5006 | 3 | E | | 115-199 |
| 0002 | 22 | | GA | | 6-0 | 24-51-31 | C00613 | =B | D | | TB5006 | 2 | E | | 115-199 |
| 0007 | 22 | | GA | | 1-0 | 24-51-31 | TB0111A | C003 | 2 | | TB0111A | C007 | 2 | | 115-199 |
| 0008 | 22 | | GA | | 1-0 | 24-51-31 | TB0111A | C007 | 2 | | TB0111A | C008 | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0122 | 286N0122 | | | | P11-2 MODULE WIRING - CENTER BUSSES (continued) | | | | | | | | | | | | |
| 0009 | 22 | | GA | | 8-0 | 24-51-31 | TB0111A | C008 | 2 | | | TB5006 | 1 | E | | 115-199 | |
| ZZAB | 03 | | ZB | | 0-0 | 24-51-31 | C00613 | =B | D | | | C01525 | =B | D | | 115-199 | |
| ZZOA | 00 | | ZB | | 0-0 | 24-51-31 | C00613 | =B | D | | | C00602 | =B | D | | 115-199 | |
| ZZOB | 00 | | ZB | | 0-0 | 24-51-31 | C00602 | =B | D | | | C01525 | =B | D | | 115-199 | |
| ZZXA | 02 | | ZA | | 0-4 | 24-51-31 | C00602 | =B | D | | | C00515 | =B | D | | 115-199 | |
| W0124 | 286N0124 | | | | P11-1 MODULE WIRING - LEFT - STBY - LOAD SIDE | | | | | | | | | | | | |
| 0001 | 24 | | GK | | 8-0 | 30-31-11 | C01120 | =L | D | | | D40622J | 12 | | | 001-099 | |
| 0008 | 24 | | GK | | 9-0 | 25-58-11 | C01522 | =L | D | * | | D40748J | 8 | | | 001-099 | |
| 0008 | 22 | | GA | | 9-0 | 27-58-11 | C01522 | =L | D | * | | D40748J | 8 | | | 115-199 | |
| 0009 | 24 | | GK | | 6-0 | 27-58-11 | C01522 | =L | D | * | | D40616J | 9 | | | 001-099 | |
| 0009 | 22 | | GA | | 5-0 | 27-58-11 | C01522 | =L | D | * | | D40616J | 9 | | | 115-199 | |
| 0010 | 24 | | GK | | 6-0 | 27-58-11 | C01008 | =L | D | * | | D40616J | 10 | | | 001-099 | |
| 0010 | 22 | | GA | | 5-0 | 27-58-11 | C01008 | =L | D | * | | D40616J | 10 | | | 115-199 | |
| 0011 | 24 | | GK | | 9-0 | 27-58-11 | C01008 | =L | D | * | | D40748J | 18 | | | 001-099 | |
| 0011 | 22 | | GA | | 9-0 | 27-58-11 | C01008 | =L | D | * | | D40748J | 18 | | | 115-199 | |
| 0012Y | 22 | | QB | | 7-0 | 27-41-11 | C01017 | =L | D | | | D40610J | 12 | | | 001-099 | |
| 0012Y | 22 | | QB | | 6-0 | 27-41-11 | C01017 | =L | D | | | D40610J | 12 | | | 115-199 | |
| 0013 | 22 | | GA | | 8-0 | 34-21-11 | C00611 | =L | D | | | D40610J | 13 | | | ALL | |
| 0014 | 20 | | GA | | 7-0 | 22-31-12 | C00512 | =L | D | | | D40610J | 14 | | | 001-099 | |
| 0014 | 20 | | GA | | 6-0 | 22-31-12 | C00512 | =L | D | | | D40610J | 14 | | | 115-199 | |
| 0015 | 20 | | GA | | 7-0 | 22-31-12 | C00525 | =L | D | | | D40610J | 15 | | | 001-099 | |
| 0015 | 20 | | GA | | 6-0 | 22-31-12 | C00525 | =L | D | | | D40610J | 15 | | | 115-199 | |
| 0016 | 20 | | GA | | 7-0 | 22-31-11 | C00501 | =L | D | | | D40610J | 16 | | | ALL | |
| 0017 | 20 | | GA | | 7-0 | 22-11-11 | C00513 | =L | D | | | D40610J | 17 | | | 001-099 | |
| 0017 | 20 | | GA | | 6-0 | 22-11-11 | C00513 | =L | D | | | D40610J | 17 | | | 115-199 | |
| 0018 | 22 | | GA | | 7-0 | 34-31-11 | C00603 | =L | D | | | D40610J | 8 | | | 001-099 | |
| 0018 | 22 | | GA | | 7-0 | 34-31-11 | C04600 | =L | D | | | D40610J | 8 | | | 115-199 | |
| 0019 | 22 | | GA | | 7-0 | 34-22-16 | C00637 | =L | D | | | D40610J | 19 | | | ALL | |
| 0020 | 20 | | GA | | 7-0 | 22-11-12 | C00516 | =L | D | | | D40610J | 20 | | | 001-099 | |
| 0020 | 20 | | GA | | 6-0 | 22-11-12 | C00516 | =L | D | | | D40610J | 20 | | | 115-199 | |
| 0021 | 20 | | GA | | 6-0 | 22-11-12 | C00522 | =L | D | | | D40610J | 21 | | | ALL | |
| 0022 | 20 | | GA | | 7-0 | 34-61-11 | C00609 | =L | D | | | D40610J | 22 | | | ALL | |
| 0023 | 20 | | GA | | 9-0 | 34-61-11 | C00597 | =L | D | | | D40800P | 27 | | | ALL | |
| 0024 | 22 | | GA | | 8-0 | 34-46-11 | C00592 | =L | D | | | D40610J | 24 | | | 001-099 | |
| 0024 | 22 | | GA | | 7-0 | 34-46-11 | C00592 | =L | D | | | D40610J | 24 | | | 115-199 | |
| 0025 | 24 | | GK | | 8-0 | 78-36-11 | C01480 | =L | D | | | D40838J | 13 | | | 001-099 | |
| 0026 | 22 | | GA | | 7-0 | 23-21-11 | C00539 | =L | D | | | D40610J | 26 | | | ALL | |
| 0027 | 22 | | GA | | 7-0 | 34-33-11 | C00600 | =L | D | | | D40610J | 27 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0124 | 286N0124 | | | P11-1 MODULE WIRING - LEFT - STBY - LOAD SIDE (continued) | | | | | | | | | | | |
| 0029 | 22 | GA | | | 7-0 | 34-55-11 | C00582 | =L | D | | D40610J | 29 | | | 001-099 |
| 0029 | 22 | GA | | | 9-0 | 34-55-11 | C00582 | =L | D | | D40798P | 20 | | | 115-199 |
| 0031 | 22 | GA | | | 7-0 | 34-22-16 | C00622 | =L | D | | D40622J | 13 | | | 001-099 |
| 0032 | 22 | GA | | | 7-0 | 27-21-12 | C01031 | =L | D | | D40622J | 29 | | | 001-003 |
| 0032 | 22 | GA | | | 8-0 | 27-21-12 | C01031 | =L | D | | D40622J | 29 | | | 004, 115-199 |
| 0032 | 22 | GA | | | 7-0 | 27-21-12 | C01031 | =L | D | | D40622J | 24 | | | 005-099 |
| 0033 | 20 | GA | | | 8-0 | 34-43-11 | C00615 | =L | D | | D40610J | 33 | | | 001-099 |
| 0033 | 20 | GA | | | 7-0 | 34-43-11 | C00615 | =L | D | | D40610J | 33 | | | 115-199 |
| 0036 | 24 | GK | | | 6-0 | 27-51-41 | C01025 | =L | D | | D40610J | 36 | | | 001-099 |
| 0036 | 22 | GA | | | 6-0 | 27-51-41 | C01025 | =L | D | | D40610J | 36 | | | 115-199 |
| 0037 | 22 | GA | | | 7-0 | 34-12-11 | C00002 | =L | D | | D40610J | 37 | | | ALL |
| 0038 | 22 | GA | | | 8-0 | 34-12-11 | C00001 | =L | D | | D40610J | 38 | | | ALL |
| 0039 | 22 | GA | | | 7-0 | 34-22-36 | C00639 | =L | D | | D40610J | 39 | | | ALL |
| 0040 | 20 | GA | | | 7-0 | 21-51-11 | C00653 | =L | D | | D40616J | 6 | | | 001-099 |
| 0041 | 22 | GA | | | 7-0 | 27-51-31 | C04110 | =L | D | | D40622J | 27 | | | 001-099 |
| 0043 | 24 | GK | | | 6-0 | 27-51-41 | C01539 | =L | D | | D40610J | 43 | | | 001-099 |
| 0043 | 20 | GA | | | 6-0 | 27-51-41 | C01539 | =L | D | | D40610J | 43 | | | 115-199 |
| 0044 | 22 | GA | | | 9-0 | 34-53-11 | C04051 | =L | D | | D40798P | 12 | | | ALL |
| 0047 | 24 | GK | | | 6-0 | 27-51-41 | C01037 | =L | D | | D40610J | 47 | | | 001-099 |
| 0047 | 22 | GA | | | 6-0 | 27-51-41 | C01037 | =L | D | | D40610J | 47 | | | 115-199 |
| 0050 | 20 | GA | | | 7-0 | 23-11-11 | C03005 | A1 | D | | D40610J | 51 | | | ALL |
| 0051 | 20 | GA | | | 7-0 | 23-11-11 | C03005 | B1 | D | | D40610J | 52 | | | ALL |
| 0052 | 20 | GA | | | 7-0 | 23-11-11 | C03005 | C1 | D | * | D40610J | 53 | | | ALL |
| 0065 | 22 | GA | | | 5-0 | 27-48-21 | C01523 | =L | D | | D40616J | 5 | | | ALL |
| 0072 | 22 | GA | | | 9-0 | 34-57-11 | C00607 | =L | D | | D40798P | 3 | | | ALL |
| 0079 | 20 | GA | | | 1-0 | 34-12-11 | C00001 | =B | D | * | C00002 | =B | D | | 001-099 |
| 0079 | 20 | GA | | | 2-0 | 34-12-11 | C00001 | =B | D | * | C00002 | =B | D | | 115-199 |
| 0080 | 20 | GA | | | 8-0 | 34-12-11 | C00001 | =B | D | * | D40610J | 50 | | | ALL |
| 0081 | 24 | GK | | | 10-0 | 30-32-11 | C04194 | =L | D | | D40806P | 38 | | | 001-099 |
| 0093 | 22 | GA | | | 7-0 | 34-25-11 | C04263 | =L | D | | D40610J | 3 | | | 001, 003-099, 115-199 |
| 0101 | 22 | GA | | | 6-0 | 27-09-11 | C01531 | =L | D | | D40610J | 7 | | | 001-099 |
| 0101 | 22 | GA | | | 5-0 | 27-09-11 | C01531 | =L | D | | D40610J | 7 | | | 115-199 |
| 0102 | 22 | GA | | | 5-0 | 27-09-11 | C01536 | =L | D | | D40610J | 10 | | | ALL |
| 0103 | 22 | GA | | | 11-0 | 31-25-11 | C00573 | =L | D | | D40752J | 7 | | | 001-099 |
| 0106 | 22 | GA | | | 7-0 | 27-48-11 | C01002 | =L | D | | D40610J | 46 | | | 001-099 |
| 0106 | 22 | GA | | | 6-0 | 27-48-11 | C01002 | =L | D | | D40610J | 46 | | | 115-199 |
| 0110 | 16 | GA | | | 7-0 | 23-12-31 | C00546 | =L | D | | D40610J | 40 | 16 | | 001-099 |
| 0116 | 22 | GA | | | 11-0 | 34-57-21 | C04118 | =L | D | | D40806P | 39 | | | 001-099 |
| 0119 | 20 | GA | | | 12-0 | 34-12-61 | C04664 | =L | D | | D40752J | 5 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | To | | | | | | |
|------------------------|-------------|-------|-----|---|----------|---------|--------|------|--------|-------|------|---------|--------|-------------|---|---------|
| | GA | CO TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W0124 | 286N0124 | | | P11-1 MODULE WIRING - LEFT - STBY - LOAD SIDE (continued) | | | | | | | | | | | | |
| 0122 | 20 | GA | | 9-0 | 27-62-11 | | C01023 | =L | D | * | | D40800P | 22 | | | ALL |
| 0123 | 20 | GA | | 8-0 | 34-45-01 | | C04443 | =L | D | | | D40610J | 48 | | | 001-099 |
| 0123 | 20 | GA | | 7-0 | 34-45-01 | | C04443 | =L | D | | | D40610J | 48 | | | 115-199 |
| 0124 | 20 | GA | | 12-0 | 34-12-62 | | C04665 | =L | D | | | D40752J | 6 | | | 001-099 |
| 0141 | 20 | GA | | 6-0 | 27-62-11 | | C01023 | =L | D | * | | D40616J | 4 | | | ALL |
| 0164 | 22 | GA | | 8-0 | 34-46-14 | | C04509 | =L | D | * | | D40616J | 12 | | | 002 |
| 0177 | 22 | GA | | 8-0 | 34-43-14 | | C04509 | =L | D | * | | D40610J | 44 | | | 002 |
| 0202 | 24 | GK | | 11-0 | 34-13-11 | | C00580 | =L | D | | | D40748J | 12 | | | ALL |
| 0203 | 22 | GA | | 11-0 | 34-13-11 | | C00584 | =L | D | | | D40748J | 13 | | | 001-099 |
| 0203 | 22 | GA | | 10-0 | 34-13-11 | | C00584 | =L | D | | | D40748J | 13 | | | 115-199 |
| 0204 | 22 | GA | | 10-0 | 34-22-16 | | C00633 | =L | D | | | D40800P | 51 | | | ALL |
| 0214 | 22 | GA | | 10-0 | 34-22-82 | | C00586 | =L | D | | | D40748J | 14 | | | ALL |
| 0302 | 22 | GA | | 10-0 | 34-61-15 | | C00641 | =L | D | | | D40748J | 22 | | | 001-099 |
| 0302 | 22 | PA | | 10-0 | 34-61-15 | | C00725 | =L | D | | | D40622J | 36 | | | 115-199 |
| 0315 | 22 | GA | | 8-0 | 27-23-11 | | C04035 | =L | D | | | D40798P | 1 | | | ALL |
| 0316 | 22 | GA | | 8-0 | 27-23-11 | | C04033 | =L | D | | | D40800P | 28 | | | ALL |
| 0350 | 22 | GA | | 10-0 | 34-22-16 | | C00588 | =L | D | | | D40748J | 15 | | | ALL |
| 0351 | 22 | GA | | 11-0 | 34-22-16 | | C00593 | =L | D | | | D40748J | 19 | | | 001-099 |
| 0351 | 22 | GA | | 10-0 | 34-22-16 | | C00593 | =L | D | | | D40748J | 19 | | | 115-199 |
| 0353 | 20 | GA | | 9-0 | 23-11-11 | | C03005 | C1 | D | * | | D40798P | 9 | | | 001-099 |
| 0353 | 20 | GA | | 9-0 | 23-11-11 | | C03005 | C1 | D | * | | D40798P | 7 | | | 115-199 |
| 0402 | 16 | GA | | 5-0 | 33-13-61 | | L00286 | =G | G | | | GD00601 | AC.. | 2 | | 001-099 |
| 0402 | 16 | GA | | 8-0 | 33-13-61 | | L00286 | =G | G | | | GD00601 | AC.. | 2 | | 115-199 |
| 0403 | 20 | GA | | 1-0 | 33-13-61 | | L00289 | =P | B | * | | L00290 | =P | B | * | 001-099 |
| 0403 | 20 | GA | | 2-0 | 33-13-61 | | L00289 | =P | B | * | | L00290 | =P | B | * | 115-199 |
| 0404 | 20 | GA | | 2-0 | 33-13-61 | | L00290 | =P | B | * | | L00429 | =P | B | | ALL |
| 0405 | 20 | GA | | 2-0 | 33-13-61 | | L00283 | =P | B | | | L00284 | =P | B | * | ALL |
| 0406 | 20 | GA | | 2-0 | 33-13-61 | | L00284 | =P | B | * | | L00285 | =P | B | * | ALL |
| 0407 | 20 | GA | | 2-0 | 33-13-61 | | L00285 | =P | B | * | | L00286 | =P | B | | ALL |
| 0408 | 20 | GA | | 2-0 | 33-13-61 | | L00287 | =P | B | | | L00288 | =P | B | * | ALL |
| 0410 | 20 | GA | | 2-0 | 33-13-61 | | L00289 | =P | B | * | | L00288 | =P | B | * | ALL |
| 0411 | 22 | GA | | 10-0 | 78-34-11 | | C01482 | =L | D | | | D40806P | 40 | | | 001-099 |
| 0506 | 24 | GK | | 10-0 | 21-51-12 | | C00702 | =L | D | | | D40806P | 37 | | | 001-099 |
| 0528 | 20 | GA | | 9-0 | 21-51-23 | | C04039 | =L | D | * | | D40800P | 43 | | | 001-099 |
| 0628 | 20 | GA | | 7-0 | 21-51-23 | | C04039 | =L | D | * | | D40616J | 8 | | | 001-099 |
| 0702 | 22 | GA | | 8-0 | 27-09-11 | | C01538 | =L | D | | | D40622J | 2 | | | 001-099 |
| 0704 | 22 | GA | | 8-0 | 27-09-11 | | C01534 | =L | D | | | D40622J | 4 | | | 001-099 |
| 0707 | 22 | GA | | 8-0 | 34-31-31 | | C00606 | =L | D | | | D40622J | 7 | | | 001-099 |
| 0708 | 20 | GA | | 8-0 | 34-24-11 | | C00619 | =L | D | | | D40622J | 8 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|-------|------|------|---------|-------|------|------|---------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W0124 | 286N0124 | | | | P11-1 MODULE WIRING - LEFT - STBY - LOAD SIDE (continued) | | | | | | | | | | |
| 0709 | 22 | | GA | | 8-0 | 34-24-11 | C00604 | =L | D | | D40622J | 9 | | | 001-099 |
| 0710 | 20 | | GA | | 8-0 | 22-31-12 | C00521 | =L | D | * | D40622J | 10 | | | 001-099 |
| 0711 | 20 | | GA | | 8-0 | 22-11-32 | C00521 | =L | D | * | D40622J | 11 | | | 001-099 |
| 0714 | 20 | | GA | | 9-0 | 34-51-11 | C00595 | =L | D | | D40622J | 14 | | | 001-099 |
| 0725 | 22 | | GA | | 8-0 | 34-12-11 | C00625 | =L | D | | D40622J | 25 | | | 001-099 |
| 0727 | 24 | | GK | | 11-0 | 36-11-31 | C01337 | =L | D | | D40806P | 25 | | | 001-099 |
| 0729 | 20 | | GA | | 10-0 | 27-21-11 | C01033 | =L | D | | D40806P | 16 | | | 001-099 |
| 0746 | 24 | | GK | | 9-0 | 36-11-31 | C01338 | =L | D | | D40624J | 17 | | | 001-099 |
| 0750 | 24 | | GK | | 10-0 | 33-13-31 | C01246 | =L | D | * | D40806P | 9 | | | 001-099 |
| 0752 | 16 | | GA | | 8-0 | 23-12-11 | C00544 | =L | D | | D40622J | 21 | | | 001-099 |
| 0753 | 24 | | GK | | 11-0 | 33-13-12 | C01246 | =L | D | * | D40752J | 3 | | | 001-099 |
| 0754 | 22 | | GA | | 11-0 | 34-13-11 | C00591 | =L | D | | D40752J | 2 | | | 001-099 |
| 0761 | 22 | | GA | | 12-0 | 34-22-81 | C00635 | =L | D | | D40752J | 1 | | | 001-099 |
| 0763 | 22 | | GA | | 8-0 | 31-51-12 | C00566 | =L | D | | D40624J | 13 | | | 001-099 |
| 0791 | 24 | | GK | | 7-0 | 27-51-61 | C01521 | =L | D | * | D40622J | 31 | | | 001-099 |
| 0792 | 24 | | GK | | 7-0 | 27-51-61 | C01541 | =L | D | | D40622J | 32 | | | 001-099 |
| 0793 | 24 | | GK | | 7-0 | 27-51-61 | C01524 | =L | D | | D40622J | 33 | | | 001-099 |
| 0794 | 24 | | GK | | 7-0 | 27-51-61 | C01521 | =L | D | * | D40622J | 34 | | | 001-099 |
| 0795 | 24 | | GK | | 7-0 | 27-51-61 | C01524 | =B | D | | D40622J | 35 | | | 001-099 |
| 0803 | 20 | | GA | | 10-0 | 21-31-31 | C00683 | =L | D | | D40806P | 3 | | | 001-099 |
| 0805 | 20 | | GA | | 10-0 | 22-21-11 | C01560 | =L | D | | D40806P | 5 | | | 001-099 |
| 0807 | 20 | | GA | | 8-0 | 74-31-11 | C01434 | =L | D | | D40622J | 37 | | | 001-099 |
| 0808 | 20 | | GA | | 8-0 | 74-31-21 | C01437 | =L | D | | D40624J | 38 | | | 001-099 |
| 0810 | 22 | | GA | | 10-0 | 31-51-11 | C00567 | =L | D | | D40806P | 10 | | | 001-099 |
| 0811 | 20 | | GA | | 10-0 | 74-31-11 | C01435 | =L | D | | D40808P | 14 | | | 001-099 |
| 0812 | 22 | | GA | | 10-0 | 33-11-11 | C01283 | =L | D | | D40806P | 2 | | | 001-099 |
| 0812 | 22 | | GA | | 11-0 | 33-11-11 | C01283 | =L | D | | D40806P | 2 | | | 115-199 |
| 0813 | 20 | | GA | | 10-0 | 74-31-21 | C01438 | =L | D | | D40806P | 11 | | | 001-099 |
| 0859 | 24 | | GK | | 10-0 | 21-33-11 | C04206 | =L | D | | D40808P | 9 | | | 001-099 |
| 0911 | 20 | | GA | | 10-0 | 21-31-11 | C00658 | =L | D | | D40806P | 20 | | | 001-099 |
| 0927 | 24 | | GK | | 10-0 | 26-17-11 | C00770 | =L | D | | D40806P | 27 | | | 001-099 |
| 0950 | 24 | | GK | | 10-0 | 24-51-31 | C00826 | =L | D | | D40806P | 45 | | | 001-099 |
| 0951 | 22 | | GA | | 8-0 | 27-32-11 | C01039 | =L | D | | D40624J | 20 | | | 001-099 |
| 0952Y | 20 | | QB | | 10-0 | 27-41-11 | C01528 | =L | D | | D40808P | 22 | | | 001-099 |
| 0953 | 22 | | GA | | 8-0 | 27-09-11 | C01533 | =L | D | | D40624J | 29 | | | 001-099 |
| 0954 | 22 | | GA | | 8-0 | 27-09-11 | C01537 | =L | D | | D40624J | 30 | | | 001-099 |
| 0957 | 24 | | GK | | 10-0 | 21-33-11 | C04205 | =L | D | | D40806P | 19 | | | 001-099 |
| 0958Y | 20 | | QB | | 10-0 | 27-41-21 | C01529 | =L | D | | D40806P | 21 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0126 | 286N0126 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT L(B) | | | | | | | | | | | |
| 0002 | 22 | | GA | | 6-0 | 36-11-12 | C04196 | =L | D | | D40614J | 2 | | | ALL |
| 0003 | 22 | | GA | | 7-0 | 27-18-11 | C04099 | =L | D | | D40612J | 10 | | | ALL |
| 0004 | 24 | | GK | | 7-0 | 21-58-21 | C00705 | =L | D | | D40800P | 20 | | | ALL |
| 0005 | 22 | | GA | | 7-0 | 33-11-21 | C04280 | =L | D | | D40800P | 16 | | | ALL |
| 0006 | 22 | | GA | | 6-0 | 32-09-11 | C01182 | =L | D | | D40614J | 6 | | | 001-099 |
| 0006 | 22 | | GA | | 6-0 | 32-09-11 | C01182 | =L | D | * | D40614J | 6 | | | 115-199 |
| 0007 | 20 | | GA | | 7-0 | 27-31-22 | C04032 | =L | D | | D40612J | 33 | | | ALL |
| 0009 | 22 | | GA | | 8-0 | 76-11-21 | C04107 | =L | D | | D40614J | 9 | | | ALL |
| 0010 | 24 | | GK | | 6-0 | 21-43-11 | C04059 | =L | D | | D40800P | 41 | | | 001-099 |
| 0010 | 24 | | GK | | 7-0 | 21-43-11 | C04059 | =L | D | | D40800P | 41 | | | 115-199 |
| 0011 | 22 | | GA | | 7-0 | 21-58-11 | C04069 | =L | D | | D40614J | 11 | | | ALL |
| 0012 | 22 | | GA | | 6-0 | 36-21-11 | C01332 | =L | D | | D40614J | 12 | | | ALL |
| 0014 | 22 | | GA | | 7-0 | 21-44-11 | C04071 | =L | D | | D40614J | 14 | | | ALL |
| 0015 | 22 | | GA | | 5-0 | 32-42-11 | C01171 | =L | D | | D40614J | 15 | | | ALL |
| 0017 | 22 | | GA | | 8-0 | 27-23-21 | C04283 | =L | D | | D40614J | 24 | | | ALL |
| 0018 | 22 | | GA | | 7-0 | 33-25-11 | C04376 | =L | D | | D40614J | 18 | | | ALL |
| 0020 | 16 | | GA | | 8-0 | 30-42-11 | C01143 | =L | D | * | D40748J | 23 | | | 001-099 |
| 0020 | 16 | | GA | | 7-0 | 30-42-11 | C01143 | =L | D | * | D40748J | 23 | | | 115-199 |
| 0022 | 22 | | GA | | 8-0 | 28-22-11 | C04679 | =L | D | | D40612J | 12 | | | ALL |
| 0023 | 22 | | GA | | 6-0 | 29-31-11 | C01082 | =L | D | | D40612J | 35 | | | 001-099 |
| 0023 | 22 | | GA | | 7-0 | 29-31-11 | C01082 | =L | D | | D40612J | 35 | | | 115-199 |
| 0024 | 22 | | GA | | 7-0 | 29-31-11 | C01080 | =L | D | | D40800P | 1 | | | ALL |
| 0025 | 22 | | GA | | 7-0 | 77-11-11 | C04103 | =L | D | | D40612J | 3 | | | ALL |
| 0028 | 20 | | GA | | 7-0 | 36-11-11 | C01339 | =L | D | | D40614J | 43 | | | ALL |
| 0029 | 20 | | GA | | 8-0 | 21-51-11 | C00653 | =L | D | | D40614J | 29 | | | 115-199 |
| 0031 | 18 | | GA | | 7-0 | 73-21-11 | C04119 | =L | D | | D40800P | 50 | 18 | | 001-099 |
| 0031 | 18 | | GA | | 8-0 | 73-21-11 | C04119 | =L | D | | D40800P | 50 | 18 | | 115-199 |
| 0033 | 24 | | GK | | 5-0 | 32-41-11 | C01180 | =L | D | | D40612J | 14 | | | ALL |
| 0039 | 22 | | GA | | 5-0 | 32-09-11 | C01182 | =L | D | * | D40798P | 19 | | | 115-199 |
| 0044 | 18 | | GA | | 7-0 | 73-21-12 | C04129 | =L | D | | D40800P | 44 | 18 | | 001-099 |
| 0044 | 18 | | GA | | 8-0 | 73-21-12 | C04129 | =L | D | | D40800P | 44 | 18 | | 115-199 |
| 0046 | 22 | | GA | | 5-0 | 32-46-11 | C01181 | =L | D | | D40612J | 26 | | | 115-199 |
| 0047 | 20 | | GA | | 15-0 | 25-31-33 | D40800P | | 13 | | D41120P | 10 | | | 001-099 |
| 0048 | 22 | | GA | | 6-0 | 31-31-01 | C00564 | =L | D | | D40612J | 30 | | | 001-099 |
| 0048 | 22 | | GA | | 7-0 | 31-31-31 | C00564 | =L | D | | D40800P | 18 | | | 115-199 |
| 0049 | 22 | | GA | | 8-0 | 32-42-11 | TB0113A | C023 | 2 | | D40614J | 39 | | | 115-199 |
| 0058 | 22 | | GA | | 7-0 | 33-13-31 | C01241 | =L | D | | D40800P | 6 | | | ALL |
| 0059 | 20 | | GA | | 8-0 | 31-41-11 | C04078 | =L | D | | D40612J | 19 | | | ALL |
| 0061 | 24 | | GK | | 7-0 | 24-51-71 | C04126 | =L | D | | D40800P | 38 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0126 | | 286N0126 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT L(B) (continued) | | | | | | | | | |
| | 0061 | 22 | GA | | 7-0 | 24-51-71 | C04126 | =L | D | | D40800P | 38 | | | 115-199 |
| | 0063 | 22 | GA | | 7-0 | 31-31-01 | C00561 | =L | D | | D40612J | 2 | | | 001-099 |
| | 0063 | 22 | GA | | 7-0 | 31-31-11 | C00561 | =L | D | | D40612J | 2 | | | 115-199 |
| | 0064 | 22 | GA | | 7-0 | 31-31-01 | C00578 | =L | D | | D40612J | 6 | | | 001-099 |
| | 0064 | 22 | GA | | 7-0 | 31-31-11 | C00578 | =L | D | | D40612J | 6 | | | 115-199 |
| | 0067 | 22 | GA | | 7-0 | 24-25-11 | C04356 | =L | D | | D40800P | 24 | | | 001-099 |
| | 0067 | 22 | GA | | 7-0 | 24-25-11 | C04356 | CAP | Y | | D40800P | 24 | | | 115-199 |
| | 0068 | 22 | GA | | 7-0 | 33-24-11 | C01254 | =L | D | | D40800P | 8 | | | ALL |
| | 0081 | 20 | GA | | 5-0 | 32-12-12 | C04178 | =L | D | | D40612J | 21 | | | ALL |
| | 0108 | 24 | GK | | 7-0 | 27-28-11 | C01005 | =L | D | | D40612J | 8 | | | 001-099 |
| | 0108 | 22 | GA | | 7-0 | 27-28-11 | C01005 | =L | D | | D40612J | 8 | | | 115-199 |
| | 0109 | 22 | GA | | 7-0 | 27-28-13 | C01034 | =L | D | | D40612J | 9 | | | ALL |
| | 0111 | 22 | GA | | 7-0 | 27-38-11 | C04101 | =L | D | | D40612J | 11 | | | ALL |
| | 0134 | 18 | GA | | 6-0 | 30-34-21 | C04298 | =L | D | | D40614J | 34 | 18 | | 001-099 |
| | 0134 | 18 | GA | | 6-0 | 30-34-21 | C04298 | =L | D | | D40614J | 55 | 18 | | 115-199 |
| | 0135 | 22 | GA | | 7-0 | 29-11-11 | C04024 | =L | D | | D40798P | 35 | | | ALL |
| | 0141 | 22 | GA | | 6-0 | 30-34-21 | C04308 | =L | D | | D40614J | 41 | | | 001-099 |
| | 0141 | 22 | GA | | 6-0 | 30-34-21 | C04308 | =L | D | | D40614J | 54 | | | 115-199 |
| | 0202 | 22 | GA | | 9-0 | 33-14-21 | C01252 | =L | D | | D40748J | 2 | | | 001-099 |
| | 0202 | 22 | GA | | 8-0 | 33-14-21 | C01252 | =L | D | | D40748J | 2 | | | 115-199 |
| | 0206 | 20 | GA | | 8-0 | 74-31-11 | C01430 | =L | D | | D40614J | 46 | | | ALL |
| | 0209 | 22 | GA | | 9-0 | 31-41-11 | C04081 | =L | D | | D40748J | 9 | | | ALL |
| | 0210 | 22 | GA | | 9-0 | 33-13-11 | C01237 | =L | D | | D40748J | 10 | | | 001-099 |
| | 0210 | 22 | GA | | 8-0 | 33-13-11 | C01237 | =L | D | | D40748J | 10 | | | 115-199 |
| | 0248 | 22 | GA | | 7-0 | 28-43-11 | C01412 | =L | + | | D40800P | 23 | | | 115-199 |
| | 0255 | 22 | GA | | 7-0 | 33-16-11 | C01297 | =L | D | | D40800P | 3 | | | 001-099 |
| | 0255 | 22 | GA | | 8-0 | 33-16-11 | C01297 | =L | D | | D40800P | 3 | | | 115-199 |
| | 0256 | 22 | GA | | 7-0 | 33-16-11 | C01290 | =L | D | | D40800P | 4 | | | ALL |
| | 0305 | 18 | GA | | 5-0 | 30-42-11 | C01143 | =L | D | * | D40798P | 23 | | | ALL |
| | 0306 | 20 | GA | | 7-0 | 33-44-21 | C01226 | =L | D | | D40798P | 6 | | | ALL |
| | 0307 | 20 | GA | | 7-0 | 33-42-21 | C01276 | =L | D | | D40800P | 7 | | | ALL |
| | 0308 | 20 | GA | | 7-0 | 33-42-12 | C01248 | =L | D | | D40798P | 7 | | | 001-099 |
| | 0309 | 22 | GA | | 5-0 | 36-21-11 | C04221 | =L | D | | D40800P | 9 | | | 001-099 |
| | 0309 | 22 | GA | | 6-0 | 36-21-11 | C04221 | =L | D | | D40800P | 9 | | | 115-199 |
| | 0310 | 20 | GA | | 7-0 | 24-51-14 | C00822 | =L | D | | D40800P | 10 | | | ALL |
| | 0311 | 22 | GA | | 7-0 | 52-51-11 | C01400 | =L | D | | D40800P | 40 | | | ALL |
| | 0312 | 22 | GA | | 7-0 | 33-13-51 | C01242 | =L | D | | D40800P | 12 | | | 001-099 |
| | 0312 | 22 | GA | | 8-0 | 33-13-51 | C01242 | =L | D | | D40800P | 12 | | | 115-199 |
| | 0313 | 24 | GK | | 13-0 | 33-13-61 | C01244 | =L | D | | TB5002 | 12 | E | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|-------------|------|--------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice | |
| W0126 | 286N0126 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT L(B) (continued) | | | | | | | | | | | |
| 0313 | 24 | | GK | | 14-0 | 33-13-61 | C01244 | =L | D | | | TB5002 | 12 | E | | 115-199 |
| 0314 | 22 | | GA | | 7-0 | 33-13-71 | C04087 | =L | D | | | D40800P | 14 | | | 115-199 |
| 0317 | 22 | | GA | | 7-0 | 33-16-21 | C01298 | =L | D | | | D40800P | 17 | | | ALL |
| 0321 | 18 | | GA | | 7-0 | 25-31-33 | C00743 | =L | D | | | D40800P | 21 | 18 | | ALL |
| 0323 | 16 | | GA | | 9-0 | 33-13-61 | L00430 | =G | G | | | GD00601 | AC.. | 2 | | 001-099 |
| 0323 | 16 | | GA | | 10-0 | 33-13-61 | L00430 | =G | G | | | GD00601 | AC.. | 2 | | 115-199 |
| 0328 | 24 | | GK | | 6-0 | 21-61-11 | C00670 | =L | D | * | | D40800P | 33 | | | 001-099 |
| 0328 | 24 | | GK | | 7-0 | 21-61-11 | C00670 | =L | D | * | | D40800P | 33 | | | 115-199 |
| 0341 | 20 | | GA | | 2-0 | 33-13-61 | L00291 | =P | B | | | L00292 | =P | B | * | ALL |
| 0342 | 20 | | GA | | 2-0 | 33-13-61 | L00292 | =P | B | * | | L00293 | =P | B | * | ALL |
| 0343 | 20 | | GA | | 2-0 | 33-13-61 | L00293 | =P | B | * | | L00294 | =P | B | | ALL |
| 0347 | 20 | | GA | | 2-0 | 33-13-61 | L00295 | =P | B | | | L00296 | =P | B | * | ALL |
| 0348 | 20 | | GA | | 2-0 | 33-13-61 | L00296 | =P | B | * | | L00297 | =P | B | * | ALL |
| 0349 | 20 | | GA | | 2-0 | 33-13-61 | L00297 | =P | B | * | | L00298 | =P | B | * | ALL |
| 0350 | 20 | | GA | | 2-0 | 33-13-61 | L00298 | =P | B | * | | L00299 | =P | B | * | ALL |
| 0351 | 20 | | GA | | 2-0 | 33-13-61 | L00299 | =P | B | * | | L00430 | =P | B | | ALL |
| 0352 | 24 | | GK | | 15-0 | 38-32-11 | C03004 | A1 | D | | | D41120P | 11 | | | 001-099 |
| 0353 | 24 | | GK | | 15-0 | 38-32-11 | C03004 | B1 | D | | | D41120P | 12 | | | 001-099 |
| 0354 | 24 | | GK | | 15-0 | 38-32-11 | C03004 | C1 | D | | | D41120P | 13 | | | 001-099 |
| 0407 | 22 | | GA | | 15-0 | 33-14-41 | D40798P | | 13 | | | D41120P | 7 | | | 001-099 |
| 0407 | 22 | | GA | | 16-0 | 33-14-41 | D40798P | | 13 | | | D41120P | 7 | | | 115-199 |
| 0411 | 20 | | GA | | 7-0 | 33-42-31 | C01271 | =L | D | | | D40800P | 37 | | | 001-099 |
| 0426 | 22 | | GA | | 7-0 | 33-11-11 | C01289 | =L | D | | | D40800P | 31 | | | ALL |
| 0444 | 22 | | GA | | 6-0 | 21-52-31 | C00709 | =L | D | | | D40612J | 44 | | | ALL |
| 0500 | 20 | | GA | | 6-0 | 22-41-11 | C00520 | =L | D | | | D40612J | 18 | | | ALL |
| 0502 | 24 | | GK | | 6-0 | 21-25-11 | C00660 | =L | D | | | D40798P | 5 | | | ALL |
| 0503 | 24 | | GK | | 7-0 | 21-61-51 | C00667 | =L | D | | | D40614J | 37 | | | ALL |
| 0504 | 20 | | GA | | 7-0 | 21-51-12 | C00673 | =L | D | | | D40614J | 16 | | | ALL |
| 0505 | 20 | | GA | | 6-0 | 21-31-11 | C00686 | =L | D | | | D40800P | 19 | | | 001-099 |
| 0505 | 20 | | GA | | 7-0 | 21-31-11 | C00686 | =L | D | | | D40800P | 19 | | | 115-199 |
| 0507 | 24 | | GK | | 7-0 | 24-51-31 | C00824 | =L | D | | | D40800P | 45 | | | 001-099 |
| 0507 | 22 | | GA | | 9-0 | 24-51-31 | C00824 | =L | D | | | TB0111A | A003 | 2 | | 115-199 |
| 0508 | 22 | | GA | | 7-0 | 27-11-11 | C01035 | =L | D | | | D40800P | 11 | | | ALL |
| 0509 | 22 | | GA | | 5-0 | 30-41-11 | C01128 | =L | D | | | D40798P | 28 | | | ALL |
| 0510 | 22 | | GA | | 5-0 | 30-43-11 | C01136 | CAP | Y | | | D40798P | 21 | | | ALL |
| 0511 | 20 | | GA | | 7-0 | 33-42-11 | C01247 | =L | D | | | D40798P | 18 | | | ALL |
| 0512 | 20 | | GA | | 7-0 | 33-42-11 | C01249 | =L | D | | | D40798P | 17 | | | ALL |
| 0516 | 22 | | GA | | 8-0 | 77-31-11 | C01464 | =L | D | | | D40612J | 4 | | | ALL |
| 0518 | 24 | | GK | | 7-0 | 79-32-11 | C01498 | =L | D | | | D40612J | 27 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|--------|---------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | Equip | Term | | Type | Splice | Equip | Term | Type | Splice | |
| W0126 | 286N0126 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT L(B) (continued) | | | | | | | | | | |
| 0518 | 22 | GA | | 7-0 | 79-32-11 | C01498 | =L | D | | D40612J | 27 | | | 115-199 |
| 0519 | 24 | GK | | 15-0 | 38-32-11 | C03003 | A1 | D | | D41120P | 1 | | | 001-099 |
| 0519 | 20 | GA | | 16-0 | 38-32-11 | C03003 | A1 | D | | D41120P | 1 | | | 115-199 |
| 0520 | 24 | GK | | 15-0 | 38-32-11 | C03003 | B1 | D | | D41120P | 2 | | | 001-099 |
| 0520 | 20 | GA | | 16-0 | 38-32-11 | C03003 | B1 | D | | D41120P | 2 | | | 115-199 |
| 0521 | 24 | GK | | 15-0 | 38-32-11 | C03003 | C1 | D | | D41120P | 3 | | | 001-099 |
| 0521 | 20 | GA | | 16-0 | 38-32-11 | C03003 | C1 | D | | D41120P | 3 | | | 115-199 |
| 0522 | 24 | GK | | 15-0 | 38-32-11 | C03043 | A1 | D | | D41120P | 4 | | | 001-099 |
| 0522 | 18 | GA | | 16-0 | 38-32-11 | C03004 | A1 | D | | D41120P | 4 | | | 115-199 |
| 0523 | 24 | GK | | 15-0 | 38-32-11 | C03043 | B1 | D | | D41120P | 5 | | | 001-099 |
| 0523 | 18 | GA | | 16-0 | 38-32-11 | C03004 | B1 | D | | D41120P | 5 | | | 115-199 |
| 0524 | 24 | GK | | 14-0 | 38-32-11 | C03043 | C1 | D | | D41120P | 6 | | | 001-099 |
| 0524 | 18 | GA | | 16-0 | 38-32-11 | C03004 | C1 | D | | D41120P | 6 | | | 115-199 |
| 0525 | 24 | GK | | 6-0 | 21-65-11 | C04019 | =L | D | | D40800P | 32 | | | ALL |
| 0527 | 20 | GA | | 7-0 | 21-51-23 | C04038 | =L | D | | D40800P | 39 | | | 001-099 |
| 0527 | 20 | GA | | 7-0 | 21-51-23 | C04038 | =L | D | | D40612J | 48 | | | 115-199 |
| 0529 | 16 | GA | | 7-0 | 29-11-31 | C04043 | =L | D | | D40800P | 46 | 16 | | ALL |
| 0530 | 16 | GA | | 7-0 | 29-11-22 | C04044 | =L | D | | D40800P | 36 | 16 | | ALL |
| 0531 | 20 | GA | | 15-0 | 33-25-21 | C04375 | =L | D | | D41120P | 8 | | | 001-099 |
| 0531 | 20 | GA | | 16-0 | 33-25-21 | C04375 | =L | D | | D41120P | 8 | | | 115-199 |
| 0532 | 24 | GK | | 6-0 | 26-18-11 | C04207 | =L | D | | D40614J | 28 | | | ALL |
| 0535 | 22 | GA | | 7-0 | 27-51-51 | C01022 | =L | D | | D40614J | 38 | | | ALL |
| 0539 | 22 | GA | | 5-0 | 32-42-11 | C01176 | =L | D | | D40798P | 14 | | | 001-099 |
| 0539 | 22 | GA | | 12-0 | 32-42-11 | C01176 | =L | D | | TB0113A | A023 | 2 | | 115-199 |
| 0599 | 20 | GA | | 6-0 | 21-61-51 | C00670 | =L | D | * | D40800P | 34 | | | 001-099 |
| 0599 | 20 | GA | | 7-0 | 21-61-51 | C00670 | =L | D | * | D40800P | 34 | | | 115-199 |
| 0601 | 22 | GA | | 6-0 | 24-51-72 | C04224 | =L | D | | D40800P | 5 | | | 001-099 |
| 0601 | 22 | GA | | 7-0 | 24-51-72 | C04224 | =L | D | | D40800P | 5 | | | 115-199 |
| 0613 | 22 | GA | | 8-0 | 27-23-21 | C04270 | =L | D | | D40614J | 13 | | | ALL |
| W0128 | 286N0128 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(A) | | | | | | | | | | |
| 0001 | 22 | GA | | 7-0 | 34-33-21 | C00601 | =L | D | | D40618J | 1 | | | ALL |
| 0002 | 16 | GA | | 7-0 | 75-31-11 | C04114 | =L | D | | D41972J | 1 | | | 001-099 |
| 0003 | 20 | GA | | 8-0 | 22-11-21 | C00514 | =L | D | | D40618J | 3 | | | ALL |
| 0004 | 22 | GA | | 8-0 | 34-31-21 | C00605 | =L | D | | D40618J | 4 | | | 001-099 |
| 0004 | 22 | GA | | 7-0 | 34-31-21 | C04601 | =L | D | | D40618J | 4 | | | 115-199 |
| 0005 | 22 | GA | | 7-0 | 34-61-21 | C00610 | =L | D | | D40618J | 5 | | | ALL |
| 0006 | 22 | GA | | 7-0 | 34-22-26 | C00638 | =L | D | | D40618J | 23 | | | ALL |
| 0007 | 20 | GA | | 8-0 | 22-11-22 | C00523 | =L | D | | D40618J | 7 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0128 | 286N0128 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(A) (continued) | | | | | | | | | | | |
| 0008 | 20 | GA | | | 7-0 | 34-21-21 | C00612 | =L | D | | D40618J | 8 | | | ALL |
| 0010 | 22 | GA | | | 7-0 | 21-51-13 | C04037 | =L | D | | D41970J | 9 | | | 001-099 |
| 0011 | 22 | GA | | | 10-0 | 33-51-11 | C01310 | =L | D | | D40808P | 26 | | | 001-099 |
| 0012 | 22 | GA | | | 10-0 | 33-51-11 | C01303 | =L | D | | D40808P | 27 | | | 001-099 |
| 0015 | 20 | GA | | | 8-0 | 22-11-22 | C00517 | =L | D | | D40618J | 15 | | | ALL |
| 0016 | 22 | GA | | | 8-0 | 34-55-21 | C00583 | =L | D | | D40618J | 16 | | | 001-099 |
| 0016 | 22 | GA | | | 9-0 | 34-55-21 | C00583 | =L | D | | D40802P | 31 | | | 115-199 |
| 0017 | 22 | GA | | | 8-0 | 34-51-21 | C00596 | =L | D | | D40618J | 37 | | | ALL |
| 0019 | 20 | GA | | | 7-0 | 21-51-21 | C00704 | =L | D | | D41970J | 4 | | | ALL |
| 0020 | 22 | GA | | | 9-0 | 34-53-21 | C04052 | =L | D | | D40802P | 29 | | | ALL |
| 0023 | 22 | GA | | | 7-0 | 34-22-26 | C00623 | =L | D | | D40618J | 6 | | | 001, 003-099, 115-199 |
| 0023 | 22 | GA | | | 7-0 | 34-22-26 | C00623 | =L | D | | D41970J | 5 | | | 002 |
| 0024 | 22 | GA | | | 9-0 | 23-43-11 | C00560 | =L | D | | D40802P | 24 | | | ALL |
| 0025 | 22 | GA | | | 8-0 | 34-12-21 | C00004 | =L | D | | D40618J | 25 | | | ALL |
| 0026 | 22 | GA | | | 8-0 | 34-12-21 | C00003 | =L | D | | D40618J | 26 | | | 001-099 |
| 0026 | 22 | GA | | | 7-0 | 34-12-21 | C00003 | =L | D | | D40618J | 26 | | | 115-199 |
| 0027 | 22 | GA | | | 7-0 | 34-12-21 | C00626 | =L | D | | D40618J | 27 | | | ALL |
| 0028 | 20 | GA | | | 7-0 | 23-71-11 | C00532 | =L | D | | D40618J | 28 | | | ALL |
| 0029 | 24 | GK | | | 7-0 | 27-81-11 | C01038 | =L | D | | D40618J | 29 | | | 001-099 |
| 0029 | 22 | GA | | | 7-0 | 27-81-11 | C01038 | =L | D | | D40618J | 29 | | | 115-199 |
| 0030 | 24 | GK | | | 7-0 | 27-81-11 | C01540 | =L | D | | D40618J | 30 | | | 001-099 |
| 0030 | 22 | GA | | | 7-0 | 27-81-11 | C01540 | =L | D | | D40618J | 30 | | | 115-199 |
| 0031 | 24 | GK | | | 7-0 | 27-81-11 | C04210 | =L | D | | D40618J | 31 | | | 001-099 |
| 0031 | 22 | GA | | | 7-0 | 27-81-11 | C04210 | =L | D | | D40618J | 31 | | | 115-199 |
| 0032 | 22 | GA | | | 9-0 | 34-61-21 | C00598 | =L | D | | D40802P | 27 | | | ALL |
| 0033 | 20 | GA | | | 8-0 | 34-12-21 | C00003 | =B | D | * | D40618J | 33 | | | ALL |
| 0034 | 20 | GA | | | 2-0 | 34-12-21 | C00003 | =B | D | * | C00004 | =B | D | | ALL |
| 0035 | 24 | GK | | | 8-0 | 78-36-21 | C01481 | =L | D | | D41972J | 12 | | | 001-002 |
| 0036 | 18 | GA | | | 7-0 | 23-32-01 | C04364 | =L | D | * | D41972J | 13 | 18 | | ALL |
| 0040 | 22 | GA | | | 8-0 | 34-22-93 | C04240 | =L | D | | D40802P | 13 | | | 115-199 |
| 0041 | 22 | GA | | | 8-0 | 34-22-93 | C04260 | =L | D | | D40802P | 14 | | | 115-199 |
| 0048 | 20 | GA | | | 9-0 | 33-13-61 | D03018 | 7 | | | GD00597 | ST.. | 2 | | 001-099 |
| 0048 | 20 | GA | | | 12-0 | 33-13-61 | D03018 | 7 | | | GD00597 | ST.. | 2 | | 115-199 |
| 0049 | 24 | GK | | | 3-0 | 33-13-61 | D03018 | 12 | | * | D03020 | 12 | | * | 001-099 |
| 0049 | 24 | GK | | | 12-0 | 33-13-61 | D03018 | 12 | | * | D03020 | 12 | | * | 115-199 |
| 0050 | 18 | GA | | | 10-0 | 33-13-61 | D03018 | 2 | 18 | | L00303 | =P | B | * | ALL |
| 0051 | 18 | GA | | | 10-0 | 33-13-61 | D03018 | 8 | 18 | | L00431 | =P | B | * | 001-099 |
| 0051 | 18 | GA | | | 9-0 | 33-13-61 | D03018 | 8 | 18 | | L00431 | =P | B | * | 115-199 |
| 0053 | 16 | GA | | | 9-0 | 33-13-61 | D03018 | 11 | 16 | | GD00597 | AC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|--|-------|-------------|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0128 | 286N0128 | P11 MODULE WIRING, CB LOAD SIDE - CAT R(A) (continued) | | | | | | | | | | | | | |
| 0053 | 16 | GA | | | 12-0 | 33-13-61 | D03018 | 11 | 16 | | GD00597 | AC.. | 2 | | 115-199 |
| 0059 | 22 | GA | | | 13-0 | 34-61-25 | C00640 | =L | D | | D40750J | | 9 | | 001-099 |
| 0072 | 24 | GK | | | 7-0 | 30-31-12 | C01121 | =L | D | | D41972J | | 8 | | 001-099 |
| 0085 | 22 | GA | | | 7-0 | 30-31-12 | C01121 | =L | D | | D41972J | | 8 | | 115-199 |
| 0086 | 20 | GA | | | 10-0 | 33-13-61 | D03016 | | 7 | | GD00597 | ST.. | 2 | | 001-099 |
| 0086 | 20 | GA | | | 13-0 | 33-13-61 | D03016 | | 7 | | GD00597 | ST.. | 2 | | 115-199 |
| 0087 | 16 | GA | | | 10-0 | 33-13-61 | D03016 | 11 | 16 | | GD00597 | AC.. | 2 | | 001-099 |
| 0087 | 16 | GA | | | 13-0 | 33-13-61 | D03016 | 11 | 16 | | GD00597 | AC.. | 2 | | 115-199 |
| 0088 | 18 | GA | | | 7-0 | 33-13-61 | D03016 | 8 | 16 | | L00294 | =P | B | | 001-099 |
| 0088 | 18 | GA | | | 9-0 | 33-13-61 | D03016 | 8 | 18 | | L00294 | =P | B | | 115-199 |
| 0089 | 18 | GA | | | 7-0 | 33-13-61 | D03016 | 2 | 18 | | L00430 | =P | B | | 001-099 |
| 0089 | 18 | GA | | | 9-0 | 33-13-61 | D03016 | 2 | 18 | | L00430 | =P | B | | 115-199 |
| 0090 | 24 | GK | | | 3-0 | 33-13-61 | D03016 | 12 | | * | D03018 | | 12 | * | 001-099 |
| 0090 | 24 | GK | | | 12-0 | 33-13-61 | D03016 | 12 | | * | D03018 | | 12 | * | 115-199 |
| 0091 | 20 | GA | | | 9-0 | 33-13-61 | D03020 | 7 | | | GD00597 | ST.. | 2 | | 001-099 |
| 0091 | 20 | GA | | | 13-0 | 33-13-61 | D03020 | 7 | | | GD00597 | ST.. | 2 | | 115-199 |
| 0092 | 24 | GK | | | 11-0 | 33-13-61 | D03020 | 12 | | * | TB5002 | | 12 | E | 001-099 |
| 0092 | 24 | GK | | | 12-0 | 33-13-61 | D03020 | 12 | | * | TB5002 | | 12 | E | 115-199 |
| 0094 | 18 | GA | | | 10-0 | 33-13-61 | D03020 | 2 | 18 | | L00286 | =P | B | | ALL |
| 0095 | 18 | GA | | | 9-0 | 33-13-61 | D03020 | 8 | 18 | | L00429 | =P | B | | ALL |
| 0096 | 16 | GA | | | 9-0 | 33-13-61 | D03020 | 11 | 16 | | GD00597 | AC.. | 2 | | 001-099 |
| 0096 | 16 | GA | | | 13-0 | 33-13-61 | D03020 | 11 | 16 | | GD00597 | AC.. | 2 | | 115-199 |
| 0099 | 22 | GA | | | 5-0 | 27-51-21 | C04212 | =L | D | | D41970J | | 1 | | ALL |
| 0100 | 20 | GA | | | 11-0 | 33-13-61 | D06486 | 7 | | | GD00597 | ST.. | 2 | | 001-099 |
| 0100 | 20 | GA | | | 14-0 | 33-13-61 | D06486 | 7 | | | GD00597 | ST.. | 2 | | 115-199 |
| 0101 | 16 | GA | | | 7-0 | 23-12-21 | C00545 | =L | D | | D40618J | | 34 | 16 | ALL |
| 0102 | 22 | GA | | | 12-0 | 34-22-91 | C00636 | =L | D | | D40750J | | 2 | | 001-099 |
| 0103 | 24 | GK | | | 8-0 | 78-36-21 | C01481 | =L | D | | D41972J | | 2 | | 003-099 |
| 0106 | 20 | GA | | | 7-0 | 23-11-21 | C03006 | A1 | D | | D40618J | | 10 | | 001-099 |
| 0106 | 20 | GA | | | 8-0 | 23-11-21 | C03006 | A1 | D | | D40618J | | 10 | | 115-199 |
| 0107 | 20 | GA | | | 8-0 | 23-11-21 | C03006 | B1 | D | | D40618J | | 11 | | ALL |
| 0108 | 20 | GA | | | 8-0 | 23-11-21 | C03006 | C1 | D | * | D40618J | | 13 | | ALL |
| 0109Y | 22 | QB | | | 7-0 | 27-41-21 | C01018 | =L | D | | D40618J | | 9 | | 001-099 |
| 0109Y | 22 | QB | | | 6-0 | 27-41-21 | C01018 | =L | D | | D40618J | | 9 | | 115-199 |
| 0110 | 16 | GA | | | 11-0 | 33-13-61 | D06486 | 11 | 16 | | GD00597 | AC.. | 2 | | 001-099 |
| 0110 | 16 | GA | | | 14-0 | 33-13-61 | D06486 | 11 | 16 | | GD00597 | AC.. | 2 | | 115-199 |
| 0111 | 18 | GA | | | 16-0 | 33-13-61 | D06486 | 2 | 18 | | L00432 | =P | B | | 001-008, 115-199 |
| 0111 | 18 | GA | | | 15-0 | 33-13-61 | D06486 | 2 | 18 | | L00432 | =P | B | | 009-099 |
| 0113 | 18 | GA | | | 17-0 | 33-13-61 | D06486 | 8 | 18 | | L00311 | =P | B | | 001-008, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|-------------|------|--------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice | |
| W0128 | 286N0128 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(A) (continued) | | | | | | | | | | | |
| 0113 | 18 | | GA | | 16-0 | 33-13-61 | D06486 | | 8 | 18 | | L00311 | =P | B | | 009-099 |
| 0115 | 22 | | GA | | 6-0 | 27-48-11 | C01009 | | =L | D | | D40618J | 35 | | | ALL |
| 0116 | 22 | | GA | | 12-0 | 34-13-21 | C00585 | | =L | D | | D40750J | 16 | | | ALL |
| 0117 | 22 | | GA | | 12-0 | 34-13-21 | C00581 | | =L | D | | D40750J | 17 | | | ALL |
| 0119 | 24 | | GK | | 3-0 | 33-13-61 | D06486 | | 12 | | | D03016 | 12 | | * | ALL |
| 0120 | 22 | | GA | | 9-0 | 23-51-11 | C00554 | | =L | D | | D40808P | 8 | | | 001-099 |
| 0120 | 22 | | GA | | 12-0 | 23-51-11 | C04256 | | =L | D | | TB0113A | A007 | 2 | | 115-199 |
| 0121 | 22 | | GA | | 9-0 | 23-51-21 | C00557 | | =L | D | | D40802P | 8 | | | 001-099 |
| 0121 | 22 | | GA | | 12-0 | 23-51-21 | C04258 | | =L | D | | TB0113A | A010 | 2 | | 115-199 |
| 0122 | 22 | | GA | | 5-0 | 27-48-21 | C01526 | | =L | D | | D41970J | 2 | | | ALL |
| 0123 | 22 | | GA | | 14-0 | 23-51-21 | TB0113A | | C009 | 2 | | D40802P | 9 | | | 115-199 |
| 0124 | 22 | | GA | | 1-0 | 23-51-21 | TB0113A | | C010 | 2 | | TB0113A | C009 | 2 | | 115-199 |
| 0129 | 22 | | GA | | 9-0 | 31-51-12 | C00568 | | =L | D | | D40802P | 30 | | | ALL |
| 0130 | 18 | | GA | | 7-0 | 23-32-01 | C04364 | | =L | D | * | D41972J | 23 | 18 | | ALL |
| 0133 | 20 | | GA | | 10-0 | 27-41-31 | C01010 | | =L | D | | D40806P | 46 | | | 001-099 |
| 0140 | 22 | | GA | | 10-0 | 24-33-12 | C04276 | | =L | D | | D40808P | 11 | | | 001-099 |
| 0141 | 20 | | GA | | 10-0 | 24-33-12 | C04276 | | =B | D | | D40808P | 21 | | | 001-099 |
| 0142 | 22 | | GA | | 11-0 | 24-33-12 | D40808P | | 17 | | | D40838J | 24 | | | 001-099 |
| 0143 | 24 | | GK | | 11-0 | 24-33-12 | D40808P | | 3 | | | D40838J | 19 | | | 001-099 |
| 0144 | 22 | | GA | | 11-0 | 24-33-12 | D40808P | | 18 | | | D40838J | 29 | | | 001-099 |
| 0145 | 22 | | GA | | 11-0 | 24-33-12 | D40808P | | 15 | | | D40838J | 22 | | | 001-099 |
| 0146 | 22 | | GA | | 8-0 | 24-33-12 | C04275 | | =L | D | | D40838J | 27 | | | 001-099 |
| 0147 | 22 | | GA | | 7-0 | 24-33-12 | D40806P | | 33 | | | D40838J | 11 | | | 001-099 |
| 0148 | 22 | | GA | | 7-0 | 24-33-12 | D40806P | | 43 | | | D40838J | 15 | | | 001-099 |
| 0149 | 24 | | GK | | 7-0 | 34-53-21 | C04423 | | =L | D | | D40618J | 54 | | | ALL |
| 0150 | 22 | | GA | | 8-0 | 32-61-11 | C04478 | | =L | D | | D40620J | 14 | | | 001-002 |
| 0150 | 22 | | GA | | 8-0 | 32-61-11 | C04478 | | =L | D | | D40838J | 2 | | | 003-099 |
| 0151 | 22 | | GA | | 7-0 | 27-09-11 | C01535 | | =L | D | | D40618J | 51 | | | ALL |
| 0152 | 22 | | GA | | 7-0 | 27-09-11 | C01532 | | =L | D | | D40618J | 52 | | | ALL |
| 0153 | 20 | | GA | | 9-0 | 28-22-32 | C04476 | | =L | D | | D40802P | 35 | | | 009-099 |
| 0154 | 20 | | GA | | 10-0 | 28-22-31 | C04485 | | =L | D | | D40808P | 34 | | | 009-099 |
| 0155 | 22 | | GA | | 8-0 | 34-61-15 | C00630 | | =L | D | | D40612J | 22 | | | 009-099 |
| 0175 | 22 | | PA | | 9-0 | 34-61-25 | C00726 | | =L | D | | D40618J | 53 | | | 115-199 |
| 0200 | 20 | | GA | | 9-0 | 23-11-21 | C03006 | | C1 | D | * | D40802P | 28 | | | ALL |
| 0205 | 22 | | GA | | 12-0 | 34-22-92 | C00587 | | =L | D | | D40750J | 5 | | | ALL |
| 0210 | 22 | | GA | | 9-0 | 27-23-11 | C04034 | | =L | D | | D40802P | 10 | | | 001-099 |
| 0210 | 22 | | GA | | 8-0 | 27-23-11 | C04034 | | =L | D | | D40802P | 10 | | | 115-199 |
| 0219 | 16 | | GA | | 5-0 | 33-13-61 | L00431 | | =G | G | | GD00611 | AC.. | 2 | | 001-099 |
| 0219 | 16 | | GA | | 10-0 | 33-13-61 | L00431 | | =G | G | | GD00611 | AC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0128 | 286N0128 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(A) (continued) | | | | | | | | | | | |
| 0224 | 22 | | GA | | 11-0 | 30-11-11 | C01132 | =L | D | | D40806P | 34 | | | 001-008, 115-199 |
| 0224 | 22 | | GA | | 10-0 | 30-11-11 | C01132 | =L | D | | D40806P | 34 | | | 009-099 |
| 0229 | 22 | | GA | | 14-0 | 23-51-21 | TB0113A | C010 | 2 | | D40802P | 32 | | | 115-199 |
| 0237 | 20 | | GA | | 2-0 | 33-13-61 | L00304 | =P | B | | L00305 | =P | B | * | ALL |
| 0238 | 20 | | GA | | 2-0 | 33-13-61 | L00305 | =P | B | * | L00306 | =P | B | * | ALL |
| 0239 | 20 | | GA | | 2-0 | 33-13-61 | L00306 | =P | B | * | L00307 | =P | B | * | ALL |
| 0240 | 20 | | GA | | 1-0 | 33-13-61 | L00307 | =P | B | * | L00431 | =P | B | * | 001-099 |
| 0240 | 20 | | GA | | 2-0 | 33-13-61 | L00307 | =P | B | * | L00431 | =P | B | * | 115-199 |
| 0242 | 24 | | GK | | 11-0 | 21-51-22 | C00703 | =L | D | | D40806P | 36 | | | ALL |
| 0248 | 20 | | GA | | 2-0 | 33-13-61 | L00300 | =P | B | | L00301 | =P | B | * | ALL |
| 0249 | 20 | | GA | | 2-0 | 33-13-61 | L00301 | =P | B | * | L00302 | =P | B | * | ALL |
| 0250 | 20 | | GA | | 2-0 | 33-13-61 | L00302 | =P | B | * | L00303 | =P | B | * | ALL |
| 0270 | 22 | | GA | | 10-0 | 78-34-21 | C01483 | =L | D | | D40808P | 34 | | | 001-002 |
| 0270 | 22 | | GA | | 10-0 | 78-34-21 | C01483 | =L | D | | D40808P | 31 | | | 003-099 |
| 0309 | 22 | | GA | | 9-0 | 34-22-26 | C00634 | =L | D | | D40802P | 5 | | | 001-099 |
| 0309 | 22 | | GA | | 8-0 | 34-22-26 | C00634 | =L | D | | D40802P | 5 | | | 115-199 |
| 0310 | 22 | | GA | | 13-0 | 34-22-26 | C00589 | =L | D | | D40750J | 4 | | | 001-099 |
| 0310 | 22 | | GA | | 12-0 | 34-22-26 | C00589 | =L | D | | D40750J | 4 | | | 115-199 |
| 0311 | 22 | | GA | | 12-0 | 34-22-26 | C00594 | =L | D | | D40750J | 3 | | | ALL |
| 0351 | 24 | | GK | | 5-0 | 27-51-31 | C04271 | =L | D | | D41970J | 8 | | | 001-099 |
| 0351 | 22 | | GA | | 5-0 | 27-51-31 | C04271 | =L | D | | D41970J | 8 | | | 115-199 |
| 0355 | 22 | | GA | | 9-0 | 22-21-21 | C01561 | =L | D | | D40802P | 7 | | | ALL |
| 0400 | 22 | | GA | | 10-0 | 30-21-11 | C01147 | =L | D | * | D40806P | 30 | | | 001-099 |
| 0402 | 20 | | GA | | 4-0 | 25-31-21 | D40802P | 2 | | | D41970J | 7 | | | 115-199 |
| 0405 | 22 | | GA | | 8-0 | 30-21-11 | C01147 | =L | D | * | D40838J | 9 | | | 001-099 |
| 0406 | 22 | | GA | | 7-0 | 30-21-11 | C01148 | =L | D | * | D41972J | 14 | | | 001-099 |
| 0407 | 22 | | GA | | 10-0 | 30-21-11 | C01148 | =L | D | * | D40808P | 5 | | | 001-099 |
| 0412 | 16 | | GA | | 8-0 | 75-31-11 | C04113 | =L | D | | D40838J | 4 | | | 001-099 |
| 0702 | 16 | | GA | | 7-0 | 35-21-11 | C01322 | =L | D | | D41972J | 32 | | | 001-099 |
| 0703 | 24 | | GK | | 7-0 | 35-21-11 | C01323 | =L | D | | D41972J | 3 | | | 001-099 |
| 0704 | 24 | | GK | | 7-0 | 35-21-11 | C01325 | =L | D | | D41972J | 10 | | | 001-099 |
| 0707 | 16 | | GA | | 7-0 | 35-21-11 | C01321 | =L | D | | D41972J | 27 | | | 001-099 |
| 0708 | 12 | | HA | | 7-7 | 28-25-11 | C01058 | =L | D | | D40838J | 6 | | | 001-099 |
| 0710 | 24 | | GK | | 9-0 | 28-25-11 | C01052 | =L | D | * | D40838J | 32 | | | 001-099 |
| 0712 | 22 | | GA | | 8-0 | 23-42-11 | C00551 | =L | D | | D40838J | 12 | | | 001-099 |
| 0714 | 24 | | GK | | 10-0 | 28-25-11 | C01052 | =L | D | * | D40808P | 2 | | | 001-099 |
| 0715 | 24 | | GK | | 10-0 | 26-11-21 | C00784 | =L | D | | D40808P | 7 | | | 001-099 |
| 0716 | 24 | | GK | | 11-0 | 28-25-11 | D40838J | 30 | | | D40808P | 1 | | | 001-099 |
| 0718 | 24 | | GK | | 10-0 | 26-15-11 | C00785 | =L | D | | D40808P | 12 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0128 | 286N0128 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(A) (continued) | | | | | | | | | | | |
| 0720 | 22 | | GA | | 10-0 | 29-11-21 | C04025 | =L | D | | D40808P | 24 | | | 001-099 |
| 0721 | 22 | | GA | | 11-0 | 32-42-11 | C01183 | =L | D | | D40806P | 29 | | | 001-099 |
| 0722 | 22 | | GA | | 11-0 | 32-42-11 | C01184 | =L | D | | D40806P | 31 | | | 001-099 |
| 0723 | 22 | | GA | | 9-0 | 28-21-11 | C01048 | =L | D | | D40838J | 3 | | | 001-099 |
| 0725 | 22 | | GA | | 11-0 | 29-22-11 | C04054 | =L | D | | D40806P | 8 | | | 001-099 |
| 0726 | 22 | | GA | | 8-0 | 32-61-11 | C01175 | =L | D | | D40838J | 31 | | | 001-099 |
| 0727 | 22 | | GA | | 11-0 | 33-16-61 | C01306 | =L | D | | D40806P | 22 | | | 001-099 |
| 0728 | 24 | | GK | | 11-0 | 26-17-11 | C04290 | =L | D | | D40806P | 35 | | | 001-099 |
| 0746 | 22 | | GA | | 11-0 | 77-12-41 | C04251 | =L | D | | D40806P | 1 | | | 001-099 |
| 0747 | 22 | | GA | | 8-0 | 77-12-42 | C04252 | =L | D | | D41972J | 7 | | | 001-099 |
| 0751 | 18 | | GA | | 8-0 | 23-31-11 | C00548 | =L | D | | D40838J | 10 | | | 001-099 |
| 0772 | 22 | | GA | | 10-0 | 23-51-11 | C00552 | =L | D | | D40808P | 23 | | | 001-099 |
| 0800 | 24 | | GK | | 10-0 | 26-11-11 | C00774 | =L | D | | D40806P | 28 | | | 001-099 |
| 0804 | 22 | | GA | | 7-0 | 80-11-21 | C01511 | =L | D | | D41972J | 15 | | | 001-099 |
| 0805 | 20 | | GA | | 10-0 | 28-22-31 | C01051 | =L | D | | D40808P | 28 | | | 001-008 |
| 0805 | 20 | | GA | | 10-0 | 28-22-31 | C04477 | =L | D | | D40808P | 28 | | | 009-099 |
| 0806 | 22 | | GA | | 11-0 | 33-16-61 | C01308 | =L | D | | D40806P | 23 | | | 001-099 |
| 0807 | 22 | | GA | | 11-0 | 33-16-61 | C01201 | =L | D | | D40806P | 24 | | | 001-099 |
| 0811 | 22 | | GA | | 10-0 | 33-11-31 | C01214 | =L | D | | D40808P | 20 | | | 001-099 |
| 0818 | 22 | | GA | | 9-0 | 28-22-21 | C04132 | =L | D | | D40838J | 18 | | | 001-099 |
| 0820 | 22 | | GA | | 9-0 | 23-51-21 | C00553 | =L | D | | D40802P | 9 | | | 001-099 |
| 0852 | 24 | | GK | | 10-0 | 26-11-11 | C00783 | =L | D | | D40808P | 16 | | | 001-099 |
| 0853 | 24 | | GK | | 11-0 | 26-15-12 | C00796 | =L | D | | D40806P | 17 | | | 001-099 |
| 0854 | 24 | | GK | | 10-0 | 26-15-11 | C00776 | =L | D | | D40806P | 15 | | | 001-099 |
| 0856 | 24 | | GK | | 10-0 | 26-11-21 | C00775 | =L | D | | D40806P | 14 | | | 001-099 |
| 0862 | 22 | | GA | | 11-0 | 33-16-51 | C01307 | =L | D | | D40806P | 12 | | | 001-099 |
| 0863 | 22 | | GA | | 11-0 | 33-16-51 | C01200 | =L | D | | D40806P | 13 | | | 001-099 |
| 0865 | 24 | | GK | | 8-0 | 21-58-12 | C04085 | =L | D | * | D40838J | 5 | | | 001-099 |
| 0901 | 12 | | HA | | 7-2 | 29-21-31 | C04216 | =L | D | | D40838J | 1 | | | 001-099 |
| 0902 | 24 | | GK | | 10-0 | 26-16-11 | C00772 | =L | D | | D40808P | 10 | | | 001-099 |
| 0908 | 16 | | GA | | 9-0 | 49-61-11 | C01390 | =L | D | | D40838J | 8 | | | 001-099 |
| 0909 | 22 | | GA | | 8-0 | 80-11-11 | C01510 | =L | D | | D40838J | 7 | | | 001-099 |
| 0910 | 22 | | GA | | 8-0 | 29-11-11 | C04023 | =L | D | | D40838J | 28 | | | 001-099 |
| 0911 | 22 | | GA | | 7-0 | 29-21-31 | C04061 | =L | D | | D41972J | 11 | | | 001-099 |
| 0915 | 22 | | GA | | 9-0 | 28-22-21 | C04133 | =L | D | | D40838J | 14 | | | 001-099 |
| 0916 | 24 | | GK | | 10-0 | 77-12-11 | C04151 | =L | D | | D40806P | 18 | | | 001-099 |
| 0918 | 22 | | GA | | 9-0 | 28-25-21 | C04175 | =L | D | | D40838J | 16 | | | 001-099 |
| 0920 | 22 | | GA | | 8-0 | 21-58-12 | C04085 | =L | D | * | D40838J | 17 | | | 001-099 |
| 0925 | 24 | | GK | | 11-0 | 26-16-11 | C00788 | =L | D | | D40806P | 26 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|---------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0128 | 286N0128 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(A) (continued) | | | | | | | | | | | |
| 0951 | 20 | | GA | | 7-0 | 22-11-31 | C00515 | =L | D | | D40626J | 1 | | | 001-099 |
| 0953 | 20 | | GA | | 7-0 | 22-11-32 | C00524 | =L | D | | D40626J | 3 | | | 001-099 |
| 0959 | 22 | | GA | | 7-0 | 27-48-21 | C01525 | =L | D | | D40626J | 9 | | | 001-099 |
| 0960 | 22 | | GA | | 7-0 | 34-33-31 | C00602 | =L | D | | D40626J | 4 | | | 001-099 |
| 0961 | 22 | | GA | | 7-0 | 34-21-31 | C00613 | =L | D | | D40626J | 5 | | | 001-099 |
| 3000B | 24 | | GM | AI | 3-0 | 33-13-61 | D03018 | | | 5 | | D03020 | 5 | * | 001-099 |
| 3000B | 24 | | GM | AI | 12-0 | 33-13-61 | D03018 | | | 5 | * | D03020 | 5 | * | 115-199 |
| 3000R | 24 | | GM | AI | 0-0 | 33-13-61 | D03018 | | | 6 | * | D03020 | 6 | * | ALL |
| 3000Y | 24 | | GM | AI | 0-0 | 33-13-61 | D03018 | | | 1 | * | D03020 | 1 | * | ALL |
| 3001B | 24 | | GM | AL | 3-0 | 33-13-61 | D03016 | | | 5 | * | D03018 | 5 | * | 001-099 |
| 3001B | 24 | | GM | AL | 12-0 | 33-13-61 | D03016 | | | 5 | * | D03018 | 5 | * | 115-199 |
| 3001R | 24 | | GM | AL | 0-0 | 33-13-61 | D03016 | | | 6 | * | D03018 | 6 | * | ALL |
| 3001Y | 24 | | GM | AL | 0-0 | 33-13-61 | D03016 | | | 1 | * | D03018 | 1 | * | ALL |
| 3002B | 24 | | GM | AN | 13-0 | 33-13-61 | D03020 | | | 5 | * | D40802P | 38 | | 001-099 |
| 3002B | 24 | | GM | AN | 12-0 | 33-13-61 | D03020 | | | 5 | * | D40802P | 38 | | 115-199 |
| 3002R | 24 | | GM | AN | 0-0 | 33-13-61 | D03020 | | | 6 | * | D40802P | 37 | | ALL |
| 3002Y | 24 | | GM | AN | 0-0 | 33-13-61 | D03020 | | | 1 | * | D40802P | 39 | | ALL |
| 3003B | 20 | | GC | AA | 3-0 | 33-13-61 | D06486 | | | 5 | | D03016 | 5 | * | ALL |
| 3003R | 20 | | GC | AA | 0-0 | 33-13-61 | D06486 | | | 6 | | D03016 | 6 | * | ALL |
| 3003Y | 20 | | GC | AA | 0-0 | 33-13-61 | D06486 | | | 1 | | D03016 | 1 | * | ALL |

WIRE LIST

D280N032

91-21-11

Section W0120

Page 16 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0130 | 286N0130 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(B) | | | | | | | | | | | |
| 0001 | 22 | | GA | | 8-0 | 31-51-11 | C00565 | =L | D | | D40620J | 1 | | | ALL |
| 0002 | 24 | | GK | | 7-0 | 33-42-12 | C01202 | =L | D | | D40620J | 2 | | | 001-002 |
| 0002 | 24 | | GK | | 8-0 | 33-42-12 | C01202 | =L | D | | D40620J | 2 | | | 003-099 |
| 0002 | 20 | | GA | | 7-0 | 33-42-12 | C01202 | =L | D | | D40620J | 2 | | | 115-199 |
| 0003 | 22 | | GA | | 6-0 | 38-14-11 | C01355 | =L | D | | D40620J | 3 | | | ALL |
| 0005 | 24 | | GK | | 7-0 | 21-61-21 | C04185 | =L | D | * | D40620J | 17 | | | 001-099 |
| 0005 | 24 | | GK | | 7-0 | 21-61-21 | C04185 | =L | D | | D40620J | 17 | | | 115-199 |
| 0006 | 24 | | GK | | 7-0 | 21-61-31 | C04031 | =L | D | | D40620J | 6 | | | ALL |
| 0007 | 22 | | GA | | 6-0 | 27-18-11 | C04100 | =L | D | | D40824J | 10 | | | 001-002, 115-199 |
| 0007 | 22 | | GA | | 7-0 | 27-18-11 | C04100 | =L | D | | D40824J | 10 | | | 003-099 |
| 0008 | 22 | | GA | | 7-0 | 33-51-11 | C01302 | =L | D | | D40620J | 8 | | | ALL |
| 0009 | 22 | | GA | | 7-0 | 33-51-11 | C01280 | =L | D | | D40620J | 9 | | | 001-002, 115-199 |
| 0009 | 22 | | GA | | 8-0 | 33-51-11 | C01280 | =L | D | | D40620J | 9 | | | 003-099 |
| 0010 | 24 | | GK | | 6-0 | 36-11-41 | C01333 | =L | D | | D40620J | 26 | | | ALL |
| 0011 | 22 | | GA | | 5-0 | 32-09-12 | C01170 | =L | D | | D40620J | 11 | | | ALL |
| 0012 | 24 | | GK | | 5-0 | 21-44-11 | C04072 | =L | D | | D40804P | 28 | | | 001-002 |
| 0012 | 24 | | GK | | 7-0 | 21-44-11 | C04072 | =L | D | | D40804P | 28 | | | 003-099 |
| 0012 | 24 | | GK | | 6-0 | 21-44-11 | C04072 | =L | D | | D40804P | 28 | | | 115-199 |
| 0014 | 22 | | GA | | 7-0 | 21-51-13 | C04036 | =L | D | | D40620J | 42 | | | 001-099 |
| 0014 | 22 | | GA | | 5-0 | 21-51-13 | C04036 | =L | D | | D40824J | 4 | | | 115-199 |
| 0016 | 24 | | GK | | 7-0 | 21-61-11 | C04029 | =L | D | | D40620J | 16 | | | ALL |
| 0017 | 24 | | GK | | 7-0 | 21-61-21 | C04030 | =L | D | | D40620J | 5 | | | ALL |
| 0018 | 20 | | GA | | 6-0 | 36-11-21 | C01340 | =L | D | | D40804P | 32 | | | 001-002 |
| 0018 | 20 | | GA | | 5-0 | 36-11-21 | C01340 | =L | D | | D40804P | 32 | | | 003-099, 115-199 |
| 0020 | 20 | | GA | | 7-0 | 74-31-21 | C01432 | =L | D | | D40620J | 46 | | | 001-099 |
| 0020 | 22 | | GA | | 7-0 | 74-31-21 | C01432 | =L | D | | D40620J | 46 | | | 115-199 |
| 0021 | 22 | | GA | | 6-0 | 36-21-11 | C01342 | =L | D | | D40620J | 21 | | | ALL |
| 0025 | 22 | | GA | | 8-0 | 76-11-21 | C04108 | =L | D | | D40620J | 25 | | | ALL |
| 0027 | 22 | | GA | | 6-0 | 27-32-21 | C04209 | =L | D | | D40824J | 17 | | | ALL |
| 0028 | 22 | | GA | | 6-0 | 28-21-11 | C01053 | =L | D | | D40620J | 28 | | | 001-002 |
| 0028 | 22 | | GA | | 7-0 | 28-21-11 | C01053 | =L | D | | D40620J | 28 | | | 003-099, 115-199 |
| 0030 | 22 | | GA | | 8-0 | 28-22-11 | C04680 | =L | D | | D40804P | 10 | | | ALL |
| 0032 | 22 | | GA | | 5-0 | 32-61-11 | C04279 | =L | D | | D40824J | 8 | | | 001-099 |
| 0032 | 22 | | GA | | 4-0 | 32-61-11 | C04279 | =L | D | | D40824J | 8 | | | 115-199 |
| 0033 | 24 | | GK | | 7-0 | 21-61-31 | C04186 | =L | D | * | D40620J | 33 | | | 001-099 |
| 0033 | 24 | | GK | | 7-0 | 21-61-31 | C04186 | =L | D | | D40620J | 33 | | | 115-199 |
| 0034 | 22 | | GA | | 5-0 | 32-42-11 | C01172 | =L | D | | D40802P | 33 | | | 001-099 |
| 0034 | 22 | | GA | | 6-0 | 32-42-11 | C01172 | =L | D | | D40802P | 33 | | | 115-199 |
| 0037 | 22 | | GA | | 8-0 | 77-11-11 | C04104 | =L | D | | D40620J | 30 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0130

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0130 | | 286N0130 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(B) (continued) | | | | | | | | | |
| 0038 | 20 | GA | | | 6-0 | 36-11-41 | C01336 | =L | D | | D40620J | 35 | | | 001-099 |
| 0038 | 20 | GA | | | 6-0 | 36-11-41 | C01336 | =L | D | | D40620J | 38 | | | 115-199 |
| 0040 | 24 | GK | | | 7-0 | 21-61-11 | C04184 | =L | D | * | D40620J | 40 | | | 001-099 |
| 0040 | 24 | GK | | | 7-0 | 21-61-11 | C04184 | =L | D | | D40620J | 40 | | | 115-199 |
| 0041 | 18 | GA | | | 7-0 | 73-21-21 | C04127 | =L | D | | D40804P | 8 | 18 | | 001-002, 115-199 |
| 0041 | 18 | GA | | | 8-0 | 73-21-21 | C04127 | =L | D | | D40804P | 8 | 18 | | 003-099 |
| 0042 | 22 | GA | | | 6-0 | 32-09-11 | C04223 | =L | D | | D40824J | 15 | | | 001-002 |
| 0042 | 22 | GA | | | 7-0 | 32-09-11 | C04223 | =L | D | | D40824J | 15 | | | 003-099 |
| 0042 | 22 | GA | | | 6-0 | 32-01-11 | C04223 | =L | D | | D40824J | 15 | | | 115-199 |
| 0043 | 18 | GA | | | 7-0 | 73-21-22 | C04130 | =L | D | | D40804P | 41 | 18 | | 001-002, 115-199 |
| 0043 | 18 | GA | | | 8-0 | 73-21-22 | C04130 | =L | D | | D40804P | 41 | 18 | | 003-099 |
| 0044 | 22 | GA | | | 7-0 | 29-31-11 | C01081 | =L | D | | D40620J | 22 | | | 001-002, 115-199 |
| 0044 | 22 | GA | | | 8-0 | 29-31-11 | C01081 | =L | D | | D40620J | 22 | | | 003-099 |
| 0045 | 22 | GA | | | 6-0 | 30-33-11 | C04131 | =L | D | | D40620J | 45 | | | ALL |
| 0046 | 22 | GA | | | 6-0 | 29-33-11 | C01101 | =L | D | | D40824J | 19 | | | ALL |
| 0047 | 22 | GA | | | 6-0 | 29-33-11 | C04193 | =L | D | | D40824J | 35 | | | ALL |
| 0048 | 22 | GA | | | 6-0 | 29-33-11 | C04192 | =L | D | | D40824J | 36 | | | 001-099 |
| 0048 | 22 | GA | | | 5-0 | 29-33-11 | C04192 | =L | D | | D40824J | 36 | | | 115-199 |
| 0049 | 24 | GK | | | 6-0 | 36-11-22 | C04197 | =L | D | | D40620J | 49 | | | 001-002, 115-199 |
| 0049 | 24 | GK | | | 7-0 | 36-11-22 | C04197 | =L | D | | D40620J | 49 | | | 003-099 |
| 0051 | 24 | GK | | | 6-0 | 30-32-11 | C04195 | =L | D | | D40804P | 3 | | | 001-002 |
| 0051 | 24 | GK | | | 7-0 | 30-32-11 | C04195 | =L | D | | D40804P | 3 | | | 003-099 |
| 0051 | 22 | GA | | | 6-0 | 30-32-11 | C04195 | =L | D | | D40804P | 3 | | | 115-199 |
| 0053 | 24 | GK | | | 7-0 | 24-51-31 | C00825 | =L | D | | D40804P | 45 | | | 001-099 |
| 0053 | 22 | GA | | | 13-0 | 24-51-31 | C00825 | =L | D | | TB0111A | A007 | 2 | | 115-199 |
| 0055 | 22 | GA | | | 6-0 | 52-71-11 | C04144 | =L | D | | D40824J | 25 | | | 001-099 |
| 0055 | 22 | GA | | | 5-0 | 52-71-11 | C04144 | =L | D | | D40824J | 25 | | | 115-199 |
| 0059 | 22 | GA | | | 9-0 | 77-31-11 | C04317 | =L | D | | D40824J | 21 | | | 001-002 |
| 0059 | 22 | GA | | | 7-0 | 77-31-11 | C04317 | =L | D | | D40824J | 21 | | | 003-099, 115-199 |
| 0060 | 20 | GA | | | 7-0 | 21-51-22 | C00674 | =L | D | | D40620J | 36 | | | ALL |
| 0061 | 20 | GA | | | 7-0 | 29-21-32 | C04292 | =L | D | * | D40620J | 39 | | | ALL |
| 0062 | 20 | GA | | | 9-0 | 29-21-32 | C04292 | =L | D | * | D40750J | 22 | | | ALL |
| 0063 | 20 | GA | | | 7-0 | 29-21-32 | D40620J | | 12 | | D40750J | 25 | | | ALL |
| 0064 | 20 | GA | | | 13-0 | 32-42-12 | TB0113A | C024 | 2 | | D40750J | 7 | | | 115-199 |
| 0065 | 20 | GA | | | 2-0 | 32-42-12 | TB0113A | C024 | 2 | | TB0113A | C023 | 2 | | 115-199 |
| 0080 | 22 | GA | | | 6-0 | 24-25-11 | C04357 | =L | D | | D40802P | 11 | | | 001-002 |
| 0080 | 22 | GA | | | 7-0 | 24-25-11 | C04357 | =L | D | | D40802P | 11 | | | 003-099 |
| 0080 | 22 | GA | | | 7-0 | 24-25-11 | C04357 | CAP | Y | | D40802P | 11 | | | 115-199 |
| 0087 | 20 | GA | | | 4-0 | 25-31-11 | D40802P | | 25 | | D40620J | 10 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0130

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|--------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0130 | 286N0130 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(B) (continued) | | | | | | | | | | | |
| 0092 | 22 | | GA | | 13-0 | 31-31-02 | | C04459 | =L | D | | D40612J | 43 | | | 001-099 |
| 0095 | 22 | | GA | | 8-0 | 78-34-21 | | C04471 | =L | D | | D40802P | 22 | | | 001-099 |
| 0095 | 22 | | GA | | 8-0 | 78-34-21 | | C04471 | =L | | | D40802P | 22 | | | 115-199 |
| 0096 | 16 | | GA | | 8-0 | 78-34-61 | | C04470 | =L | D | | D40620J | 32 | 16 | | ALL |
| 0101 | 22 | | GA | | 9-0 | 33-13-41 | | C01240 | =L | D | | D40750J | 1 | | | ALL |
| 0106 | 22 | | GA | | 10-0 | 31-25-11 | | C00574 | =L | D | | D40750J | 6 | | | ALL |
| 0107 | 22 | | GA | | 5-0 | 32-42-12 | | C01173 | =L | D | | D40802P | 6 | | | 001-099 |
| 0107 | 20 | | GA | | 12-0 | 32-42-12 | | C01173 | =L | D | | TB0113A | A024 | 2 | | 115-199 |
| 0108 | 22 | | GA | | 10-0 | 31-41-21 | | C04082 | =L | D | | D40750J | 8 | | | ALL |
| 0111 | 22 | | GA | | 9-0 | 33-13-21 | | C01239 | =L | D | | D40750J | 11 | | | ALL |
| 0113 | 22 | | GA | | 8-0 | 32-31-11 | | C01174 | =L | D | | D40750J | 13 | | | ALL |
| 0114 | 24 | | GK | | 9-0 | 33-14-11 | | C01251 | =L | D | * | D40750J | 14 | | | ALL |
| 0115 | 22 | | GA | | 9-0 | 33-14-31 | | C01281 | =L | D | * | D40750J | 15 | | | ALL |
| 0118 | 22 | | GA | | 5-0 | 24-41-11 | | C00803 | =L | D | | D40824J | 18 | | | 001-002, 115-199 |
| 0118 | 22 | | GA | | 6-0 | 24-41-11 | | C00803 | =L | D | | D40824J | 18 | | | 003-099 |
| 0121 | 22 | | GA | | 6-0 | 27-38-11 | | C04102 | =L | D | | D40824J | 11 | | | ALL |
| 0122 | 22 | | GA | | 7-0 | 31-41-21 | | C04189 | =L | D | | D40824J | 12 | | | ALL |
| 0123 | 22 | | GA | | 7-0 | 31-41-21 | | C04079 | =L | D | | D40824J | 13 | | | ALL |
| 0202 | 20 | | GA | | 7-0 | 21-31-21 | | C00701 | =L | D | | D40804P | 25 | | | 001-099 |
| 0202 | 20 | | GA | | 6-0 | 21-31-21 | | C00701 | =L | D | | D40804P | 25 | | | 115-199 |
| 0203 | 22 | | GA | | 7-0 | 33-16-31 | | C01273 | =L | D | | D40802P | 17 | | | ALL |
| 0205 | 24 | | GK | | 7-0 | 26-11-11 | | C00763 | =L | D | | D40804P | 27 | | | 001-002 |
| 0205 | 24 | | GK | | 8-0 | 26-11-11 | | C00763 | =L | D | | D40804P | 27 | | | 003-099 |
| 0205 | 24 | | GK | | 11-0 | 26-11-11 | | C00763 | =L | D | | TB0112A | A023 | 2 | | 115-199 |
| 0207 | 20 | | GA | | 7-0 | 33-43-12 | | C01314 | =L | D | | D40804P | 7 | | | 001-099 |
| 0207 | 20 | | GA | | 6-0 | 33-43-12 | | C01314 | =L | D | | D40804P | 7 | | | 115-199 |
| 0210 | 20 | | GA | | 7-0 | 33-42-12 | | C01248 | =L | D | | D40804P | 13 | | | 115-199 |
| 0211 | 20 | | GA | | 7-0 | 33-42-12 | | C01250 | =L | D | | D40804P | 11 | | | 001-002, 115-199 |
| 0211 | 20 | | GA | | 8-0 | 33-42-12 | | C01250 | =L | D | | D40804P | 11 | | | 003-099 |
| 0213 | 24 | | GK | | 7-0 | 33-11-61 | | C01251 | =L | D | * | D40804P | 40 | | | ALL |
| 0214 | 22 | | GA | | 6-0 | 30-43-11 | | C01145 | CAP | Y | | D40804P | 14 | | | 001-099 |
| 0214 | 22 | | GA | | 5-0 | 30-43-11 | | C01145 | CAP | Y | | D40804P | 14 | | | 115-199 |
| 0215 | 20 | | GA | | 6-0 | 25-31-21 | | C00741 | =L | D | | D40804P | 9 | | | 115-199 |
| 0216 | 22 | | GA | | 7-0 | 33-11-11 | | C01288 | =L | D | | D40804P | 22 | | | ALL |
| 0218 | 18 | | GA | | 6-0 | 30-34-22 | | C04299 | =L | D | | D40620J | 18 | 18 | | ALL |
| 0219 | 22 | | GA | | 7-0 | 33-16-41 | | C01284 | =L | D | | D40802P | 19 | | | 001-099 |
| 0219 | 22 | | GA | | 8-0 | 33-16-41 | | C01284 | =L | D | | D40802P | 19 | | | 115-199 |
| 0220 | 20 | | GA | | 6-0 | 24-51-24 | | C00823 | =L | D | | D40804P | 35 | | | 001-002, 115-199 |
| 0220 | 20 | | GA | | 7-0 | 24-51-24 | | C00823 | =L | D | | D40804P | 35 | | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W0130

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0130 | | 286N0130 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(B) (continued) | | | | | | | | | |
| 0222 | 22 | GA | | | 7-0 | 31-41-19 | C04094 | =L | D | | D40804P | 5 | | | 001-002 |
| 0222 | 22 | GA | | | 8-0 | 31-41-19 | C04094 | =L | D | | D40804P | 5 | | | 003-099, 115-199 |
| 0226 | 24 | GK | | | 7-0 | 21-25-11 | C00661 | =L | D | | D40620J | 34 | | | ALL |
| 0227 | 18 | GA | | | 5-0 | 30-42-11 | C01144 | =L | D | * | D40802P | 21 | | | 001-099 |
| 0227 | 18 | GA | | | 7-0 | 30-42-11 | C01144 | =L | D | * | D40802P | 21 | | | 115-199 |
| 0228 | 16 | GA | | | 8-0 | 30-42-11 | C01144 | =L | D | * | D40750J | 23 | | | ALL |
| 0229 | 20 | GA | | | 8-0 | 33-42-21 | C01277 | =L | D | | D40804P | 29 | | | 001-099 |
| 0229 | 20 | GA | | | 7-0 | 33-42-21 | C01277 | =L | D | | D40804P | 29 | | | 115-199 |
| 0231 | 22 | GA | | | 6-0 | 30-34-22 | C04309 | =L | D | | D40620J | 31 | | | ALL |
| 0232 | 24 | GK | | | 7-0 | 21-61-11 | C04184 | =L | D | * | D40804P | 37 | | | 001-099 |
| 0232 | 24 | GK | | | 5-0 | 21-61-11 | C04253 | =L | D | | D40804P | 37 | | | 115-199 |
| 0245 | 20 | GA | | | 8-0 | 33-44-11 | C01225 | =L | D | | D40804P | 1 | | | 001-099 |
| 0245 | 20 | GA | | | 7-0 | 33-44-11 | C01225 | =L | D | | D40804P | 1 | | | 115-199 |
| 0246 | 16 | GA | | | 7-0 | 29-11-12 | C04045 | =L | D | | D40802P | 20 | 16 | | 001-099 |
| 0246 | 16 | GA | | | 8-0 | 29-11-12 | C04045 | =L | D | | D40802P | 20 | 16 | | 115-199 |
| 0247 | 22 | GA | | | 6-0 | 25-66-11 | C04183 | =L | D | | D40824J | 7 | | | ALL |
| 0248 | 24 | GK | | | 6-0 | 26-18-11 | C04208 | =L | D | | D40620J | 44 | | | ALL |
| 0250 | 20 | GA | | | 8-0 | 33-41-11 | C01227 | =L | D | | D40804P | 2 | | | 001-099 |
| 0250 | 20 | GA | | | 7-0 | 33-41-11 | C01227 | =L | D | | D40804P | 2 | | | 115-199 |
| 0251 | 22 | GA | | | 7-0 | 33-11-21 | C01287 | =L | D | | D40804P | 43 | | | ALL |
| 0255 | 22 | GA | | | 17-0 | 33-14-31 | C01281 | =L | D | * | D40748J | 17 | | | ALL |
| 0260 | 20 | GA | | | 6-0 | 33-43-11 | C01294 | =L | D | | D40804P | 12 | | | 001-002, 115-199 |
| 0260 | 20 | GA | | | 7-0 | 33-43-11 | C01294 | =L | D | | D40804P | 12 | | | 003-099 |
| 0275 | 24 | GK | | | 7-0 | 79-32-11 | C01499 | =L | D | | D40824J | 22 | | | 001-099 |
| 0275 | 22 | GA | | | 7-0 | 79-32-11 | C01499 | =L | D | | D40824J | 22 | | | 115-199 |
| 0280 | 16 | GA | | | 7-0 | 29-11-31 | C04014 | =L | D | | D40802P | 18 | 16 | | 001-099 |
| 0280 | 16 | GA | | | 8-0 | 29-11-31 | C04014 | =L | D | | D40802P | 18 | 16 | | 115-199 |
| 0285 | 24 | GK | | | 6-0 | 21-61-31 | C04186 | =L | D | * | D40804P | 21 | | | 001-002 |
| 0285 | 24 | GK | | | 7-0 | 21-61-31 | C04186 | =L | D | * | D40804P | 21 | | | 003-099 |
| 0285 | 24 | GK | | | 6-0 | 21-61-31 | C04020 | =L | D | | D40804P | 21 | | | 115-199 |
| 0290 | 24 | GK | | | 7-0 | 21-61-21 | C04185 | =L | D | * | D40804P | 38 | | | 001-099 |
| 0290 | 24 | GK | | | 6-0 | 21-61-21 | C04021 | =L | D | | D40804P | 38 | | | 115-199 |
| 0295 | 22 | GA | | | 7-0 | 29-11-21 | C04026 | =L | D | | D40804P | 33 | | | ALL |
| 0300 | 24 | GK | | | 7-0 | 26-16-21 | C00795 | =L | D | | D40620J | 41 | | | ALL |
| 0301 | 22 | GA | | | 6-0 | 25-31-11 | C00740 | =L | D | | D40802P | 26 | | | 001-002 |
| 0301 | 22 | GA | | | 7-0 | 25-31-11 | C00740 | =L | D | | D40802P | 26 | | | 003-099 |
| 0302 | 24 | GK | | | 25-0 | 38-32-11 | C03012 | A1 | D | | D40494P | 4 | | | 001-099 |
| 0302 | 18 | GA | | | 26-0 | 38-32-11 | C03012 | A1 | D | | D40494P | 4 | | | 115-199 |
| 0303 | 24 | GK | | | 25-0 | 38-32-11 | C03012 | B1 | D | | D40494P | 5 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0130

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0130 | 286N0130 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT R(B) (continued) | | | | | | | | | | | |
| 0303 | 18 | | GA | | 26-0 | 38-32-11 | C03012 | B1 | D | | D40494P | 5 | | | 115-199 |
| 0304 | 24 | | GK | | 25-0 | 38-32-11 | C03012 | C1 | D | | D40494P | 6 | | | 001-099 |
| 0304 | 18 | | GA | | 26-0 | 38-32-11 | C03012 | C1 | D | | D40494P | 6 | | | 115-199 |
| 0305 | 24 | | GK | | 25-0 | 38-32-11 | C03011 | A1 | D | | D40494P | 1 | | | 001-099 |
| 0305 | 18 | | GA | | 26-0 | 38-32-11 | C03011 | A1 | D | | D40494P | 1 | | | 115-199 |
| 0306 | 24 | | GK | | 25-0 | 38-32-11 | C03011 | B1 | D | | D40494P | 2 | | | 001-099 |
| 0306 | 18 | | GA | | 26-0 | 38-32-11 | C03011 | B1 | D | | D40494P | 2 | | | 115-199 |
| 0307 | 24 | | GK | | 25-0 | 38-32-11 | C03011 | C1 | D | | D40494P | 3 | | | 001-099 |
| 0307 | 18 | | GA | | 26-0 | 38-32-11 | C03011 | C1 | D | | D40494P | 3 | | | 115-199 |
| 0308 | 24 | | GK | | 7-0 | 26-15-11 | C00765 | =L | D | | D40804P | 17 | | | 001-002 |
| 0308 | 24 | | GK | | 8-0 | 26-15-11 | C00765 | =L | D | | D40804P | 17 | | | 003-099 |
| 0308 | 24 | | GK | | 11-0 | 26-15-11 | C00765 | =L | D | | TB0112A | A019 | 2 | | 115-199 |
| 0310 | 24 | | GK | | 7-0 | 26-11-21 | C00764 | =L | D | | D40804P | 16 | | | 001-002 |
| 0310 | 24 | | GK | | 8-0 | 26-11-21 | C00764 | =L | D | | D40804P | 16 | | | 003-099 |
| 0310 | 24 | | GK | | 12-0 | 26-11-21 | C00764 | =L | D | | TB0112A | A021 | 2 | | 115-199 |
| 0315 | 24 | | GK | | 7-0 | 26-16-21 | C00794 | =L | D | | D40620J | 15 | | | ALL |
| 0320 | 24 | | GK | | 6-0 | 26-18-11 | C04261 | =L | D | | D40620J | 20 | | | 001-002, 115-199 |
| 0320 | 24 | | GK | | 7-0 | 26-18-11 | C04261 | =L | D | | D40620J | 20 | | | 003-099 |
| 0324 | 22 | | GA | | 5-0 | 35-11-13 | C01320 | =L | D | | D40824J | 24 | | | 001-099 |
| 0324 | 22 | | GA | | 6-0 | 35-11-13 | C01320 | =L | D | | D40620J | 7 | | | 115-199 |
| 0330 | 22 | | GA | | 7-0 | 24-51-72 | C04225 | =L | D | | D40804P | 30 | | | ALL |
| 0402 | 24 | | GK | | 7-0 | 26-16-11 | C00766 | =L | D | | D40804P | 18 | | | 001-099 |
| 0402 | 24 | | GK | | 11-0 | 26-16-11 | C00766 | =L | D | | TB0112A | A017 | 2 | | 115-199 |
| 0404 | 22 | | GA | | 7-0 | 33-14-51 | C04235 | =L | D | | D40804P | 6 | | | 115-199 |
| 0417 | 16 | | GA | | 9-0 | 33-13-61 | L00432 | =G | G | | GD00610 | AC.. | 2 | | 001-099 |
| 0417 | 16 | | GA | | 10-0 | 33-13-61 | L00432 | =G | G | | GD00610 | AC.. | 2 | | 115-199 |
| 0422 | 20 | | GA | | 2-0 | 33-13-61 | L00308 | =P | B | | L00309 | =P | B | * | 001-099 |
| 0422 | 20 | | GA | | 1-0 | 33-13-61 | L00308 | =P | B | | L00309 | =P | B | * | 115-199 |
| 0423 | 20 | | GA | | 2-0 | 33-13-61 | L00310 | =P | B | * | L00309 | =P | B | * | ALL |
| 0424 | 20 | | GA | | 2-0 | 33-13-61 | L00310 | =P | B | * | L00311 | =P | B | * | ALL |
| 0426 | 20 | | GA | | 2-0 | 33-13-61 | L00312 | =P | B | | L00313 | =P | B | * | 001-099 |
| 0426 | 20 | | GA | | 1-0 | 33-13-61 | L00312 | =P | B | | L00313 | =P | B | * | 115-199 |
| 0427 | 20 | | GA | | 2-0 | 33-13-61 | L00314 | =P | B | * | L00313 | =P | B | * | ALL |
| 0428 | 20 | | GA | | 2-0 | 33-13-61 | L00314 | =P | B | * | L00315 | =P | B | * | ALL |
| 0429 | 20 | | GA | | 2-0 | 33-13-61 | L00316 | =P | B | * | L00315 | =P | B | * | ALL |
| 0430 | 20 | | GA | | 2-0 | 33-13-61 | L00316 | =P | B | * | L00432 | =P | B | | 001-099 |
| 0430 | 20 | | GA | | 1-0 | 33-13-61 | L00316 | =P | B | * | L00432 | =P | B | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0130

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0132 | | 286N0132 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT S(A) | | | | | | | | | |
| 0002 | 22 | GA | | | 8-0 | 27-09-11 | C01538 | =L | D | | D40622J | 2 | | | 115-199 |
| 0004 | 22 | GA | | | 8-0 | 27-09-11 | C01534 | =L | D | | D40622J | 4 | | | 115-199 |
| 0006 | 20 | GA | | | 12-0 | 34-12-61 | C04664 | =L | D | | D40752J | 5 | | | 115-199 |
| 0007 | 22 | GA | | | 9-0 | 34-31-31 | C04602 | =L | D | | D40622J | 7 | | | 115-199 |
| 0008 | 20 | GA | | | 8-0 | 34-24-11 | C00619 | =L | D | | D40622J | 8 | | | 115-199 |
| 0009 | 22 | GA | | | 8-0 | 34-24-11 | C00604 | =L | D | | D40622J | 9 | | | 115-199 |
| 0010 | 20 | GA | | | 8-0 | 22-31-12 | C00521 | =L | D | * | D40622J | 10 | | | 115-199 |
| 0011 | 20 | GA | | | 8-0 | 22-11-32 | C00521 | =L | D | * | D40622J | 11 | | | 115-199 |
| 0014 | 20 | GA | | | 9-0 | 34-51-11 | C00595 | =L | D | | D40622J | 14 | | | 115-199 |
| 0015 | 20 | GA | | | 12-0 | 34-12-62 | C04665 | =L | D | | D40752J | 6 | | | 115-199 |
| 0025 | 22 | GA | | | 8-0 | 34-12-11 | C00625 | =L | D | | D40622J | 25 | | | 115-199 |
| 0027 | 24 | GK | | | 11-0 | 36-11-31 | C01337 | =L | D | | D40806P | 25 | | | 115-199 |
| 0029 | 20 | GA | | | 10-0 | 27-21-11 | C01033 | =L | D | | D40806P | 16 | | | 115-199 |
| 0030 | 22 | GA | | | 12-0 | 34-22-83 | C04259 | =L | D | | D40752J | 1 | | | 115-199 |
| 0031 | 22 | GA | | | 11-0 | 34-22-83 | C04239 | =L | D | | D40806P | 7 | | | 115-199 |
| 0046 | 24 | GK | | | 9-0 | 36-11-31 | C01338 | =L | D | | D40624J | 17 | | | 115-199 |
| 0048 | 22 | GA | | | 8-0 | 30-31-11 | C01120 | =L | D | | D40622J | 18 | | | 115-199 |
| 0049 | 22 | GA | | | 11-0 | 34-57-21 | C04118 | =L | D | | D40806P | 39 | | | 115-199 |
| 0050 | 24 | GK | | | 10-0 | 21-51-12 | C00702 | =L | D | | D40806P | 37 | | | 115-199 |
| 0051 | 20 | GA | | | 8-0 | 21-51-23 | C04039 | =L | D | * | D40838J | 21 | | | 115-199 |
| 0052 | 20 | GA | | | 10-0 | 21-51-23 | C04039 | =L | D | * | D40806P | 6 | | | 115-199 |
| 0053 | 22 | GA | | | 8-0 | 27-51-31 | C04110 | =L | D | | D40838J | 26 | | | 115-199 |
| 0054 | 22 | GA | | | 10-0 | 30-32-11 | C04194 | =L | D | | D40806P | 38 | | | 115-199 |
| 0055 | 22 | GA | | | 8-0 | 34-22-16 | C00622 | =L | D | | D40622J | 12 | | | 115-199 |
| 0056 | 22 | GA | | | 10-0 | 78-34-11 | C01482 | =L | D | | D40806P | 40 | | | 115-199 |
| 0057 | 24 | GK | | | 8-0 | 78-36-11 | C01480 | =L | D | | D40838J | 13 | | | 115-199 |
| 0058 | 22 | GA | | | 11-0 | 31-25-11 | C00573 | =L | D | | D40752J | 10 | | | 115-199 |
| 0100 | 24 | GK | | | 10-0 | 33-13-31 | C01246 | =L | D | * | D40806P | 9 | | | 115-199 |
| 0102 | 16 | GA | | | 8-0 | 23-12-11 | C00544 | =L | D | | D40622J | 21 | | | 115-199 |
| 0103 | 24 | GK | | | 12-0 | 33-13-12 | C01246 | =L | D | * | D40752J | 3 | | | 115-199 |
| 0104 | 22 | GA | | | 12-0 | 34-13-11 | C00591 | =L | D | | D40752J | 2 | | | 115-199 |
| 0113 | 22 | GA | | | 8-0 | 31-51-12 | C00566 | =L | D | | D40624J | 13 | | | 115-199 |
| 0141 | 22 | GA | | | 8-0 | 27-51-61 | C01521 | =L | D | * | D40622J | 31 | | | 115-199 |
| 0142 | 22 | GA | | | 8-0 | 27-51-61 | C01541 | =L | D | | D40622J | 32 | | | 115-199 |
| 0143 | 22 | GA | | | 8-0 | 27-51-61 | C01524 | =L | D | | D40622J | 33 | | | 115-199 |
| 0144 | 22 | GA | | | 8-0 | 27-51-61 | C01521 | =L | D | * | D40622J | 34 | | | 115-199 |
| 0145 | 22 | GA | | | 8-0 | 27-51-61 | C01524 | =B | D | | D40622J | 35 | | | 115-199 |
| 0203 | 20 | GA | | | 10-0 | 21-31-31 | C00683 | =L | D | | D40806P | 3 | | | 115-199 |
| 0205 | 20 | GA | | | 10-0 | 22-21-11 | C01560 | =L | D | | D40806P | 5 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0130

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|----------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0132 | 286N0132 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT S(A) (continued) | | | | | | | | | | | |
| 0207 | 20 | | GA | | 8-0 | 74-31-11 | | C01434 | =L | D | | D40622J | 37 | | | 115-199 |
| 0208 | 22 | | GA | | 9-0 | 74-31-21 | | C01437 | =L | D | | D40624J | 38 | | | 115-199 |
| 0210 | 22 | | GA | | 10-0 | 31-51-11 | | C00567 | =L | D | | D40806P | 10 | | | 115-199 |
| 0211 | 20 | | GA | | 10-0 | 74-31-11 | | C01435 | =L | D | | D40806P | 8 | | | 115-199 |
| 0213 | 22 | | GA | | 11-0 | 74-31-21 | | C01438 | =L | D | | D40808P | 4 | | | 115-199 |
| 0259 | 24 | | GK | | 11-0 | 21-33-11 | | C04206 | =L | D | | D40808P | 9 | | | 115-199 |
| 0350 | 22 | | GA | | 10-0 | 24-51-31 | | C00826 | =L | D | | TB01111A | A008 | 2 | | 115-199 |
| 0351 | 22 | | GA | | 9-0 | 27-32-11 | | C01039 | =L | D | | D40624J | 20 | | | 115-199 |
| 0352Y | 20 | | QB | | 11-0 | 27-41-11 | | C01528 | =L | D | | D40808P | 22 | | | 115-199 |
| 0353 | 22 | | GA | | 9-0 | 27-09-11 | | C01533 | =L | D | | D40624J | 29 | | | 115-199 |
| 0354 | 22 | | GA | | 9-0 | 27-09-11 | | C01537 | =L | D | | D40624J | 30 | | | 115-199 |
| 0357 | 24 | | GK | | 10-0 | 21-33-11 | | C04205 | =L | D | | D40806P | 19 | | | 115-199 |
| 0358Y | 20 | | QB | | 10-0 | 27-41-21 | | C01529 | =L | D | | D40806P | 21 | | | 115-199 |
| 0501 | 20 | | GA | | 10-0 | 21-31-11 | | C00658 | =L | D | | D40806P | 20 | | | 115-199 |
| 0570 | 24 | | GK | | 10-0 | 26-17-11 | | C00770 | =L | D | | D40806P | 27 | | | 115-199 |
| W0134 | 286N0134 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT S(B) | | | | | | | | | | | |
| 0002 | 16 | | GA | | 7-0 | 35-21-11 | | C01322 | =L | D | | D41972J | 32 | | | 115-199 |
| 0003 | 22 | | GA | | 7-0 | 35-21-11 | | C01323 | =L | D | | D41972J | 3 | | | 115-199 |
| 0004 | 22 | | GA | | 7-0 | 35-21-11 | | C01325 | =L | D | | D41972J | 10 | | | 115-199 |
| 0005 | 16 | | GA | | 7-0 | 75-31-11 | | C04114 | =L | D | | D41972J | 1 | | | 115-199 |
| 0007 | 16 | | GA | | 7-0 | 35-21-11 | | C01321 | =L | D | | D41972J | 27 | | | 115-199 |
| 0008 | 12 | | HA | | 7-6 | 28-25-11 | | C01058 | =L | D | | D40838J | 6 | | | 115-199 |
| 0010 | 22 | | GA | | 9-0 | 28-25-11 | | C01052 | =L | D | * | D40838J | 32 | | | 115-199 |
| 0012 | 22 | | GA | | 8-0 | 23-42-11 | | C00551 | =L | D | | D40838J | 12 | | | 115-199 |
| 0014 | 22 | | GA | | 10-0 | 28-25-11 | | C01052 | =L | D | * | D40808P | 2 | | | 115-199 |
| 0015 | 24 | | GK | | 9-0 | 26-11-21 | | C00784 | =L | D | | D40808P | 7 | | | 115-199 |
| 0016 | 22 | | GA | | 10-0 | 28-25-11 | | D40808P | | 1 | | D40838J | 30 | | | 115-199 |
| 0018 | 24 | | GK | | 10-0 | 26-15-11 | | C00785 | =L | D | | D40808P | 12 | | | 115-199 |
| 0020 | 22 | | GA | | 10-0 | 29-11-21 | | C04025 | =L | D | | D40808P | 24 | | | 115-199 |
| 0021 | 22 | | GA | | 11-0 | 32-42-11 | | C01183 | =L | D | | D40806P | 29 | | | 115-199 |
| 0022 | 22 | | GA | | 11-0 | 32-42-11 | | C01184 | =L | D | | D40806P | 31 | | | 115-199 |
| 0023 | 22 | | GA | | 9-0 | 28-21-11 | | C01048 | =L | D | | D40838J | 3 | | | 115-199 |
| 0025 | 20 | | GA | | 7-0 | 29-22-11 | | C04054 | =L | D | | D41972J | 6 | | | 115-199 |
| 0026 | 22 | | GA | | 8-0 | 32-61-11 | | C01175 | =L | D | | D40838J | 31 | | | 115-199 |
| 0027 | 22 | | GA | | 11-0 | 33-16-61 | | C01306 | =L | D | | D40806P | 22 | | | 115-199 |
| 0028 | 24 | | GK | | 11-0 | 26-17-11 | | C04290 | =L | D | | D40806P | 35 | | | 115-199 |
| 0045 | 22 | | GA | | 8-0 | 32-44-11 | | C04281 | =L | D | | D40838J | 25 | | | 115-199 |
| 0046 | 22 | | GA | | 11-0 | 77-12-41 | | C04251 | =L | D | | D40806P | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0130

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W0134 | 286N0134 | | | P11 MODULE WIRING, CB LOAD SIDE - CAT S(B) (continued) | | | | | | | | | | | |
| 0047 | 22 | GA | | 8-0 | 77-12-42 | C04252 | =L | D | | D41972J | 7 | | | 115-199 | |
| 0050 | 22 | GA | | 8-0 | 21-51-13 | C04037 | =L | D | | D40838J | 20 | | | 115-199 | |
| 0053 | 22 | GA | | 10-0 | 33-51-11 | C01310 | CAP | Y | | D40808P | 26 | | | 115-199 | |
| 0054 | 22 | GA | | 10-0 | 33-51-11 | C01303 | CAP | Y | | D40808P | 27 | | | 115-199 | |
| 0055 | 22 | GA | | 12-0 | 78-34-21 | C01483 | =L | D | | D40808P | 34 | | | 115-199 | |
| 0056 | 24 | GK | | 9-0 | 78-36-21 | C01481 | =L | D | | D41972J | 9 | | | 115-199 | |
| 0063 | 22 | GA | | 8-0 | 32-61-11 | C04478 | =L | D | | D40620J | 14 | | | 115-199 | |
| 0101 | 18 | GA | | 8-0 | 23-31-11 | C00548 | =L | D | | D40838J | 10 | | | 115-199 | |
| 0104 | 24 | GK | | 12-0 | 77-12-11 | C04152 | =L | D | | D40752J | 4 | | | 115-199 | |
| 0121 | 22 | GA | | 12-0 | 23-51-11 | TB0113A | C007 | 2 | | D40808P | 8 | | | 115-199 | |
| 0122 | 22 | GA | | 10-0 | 23-51-11 | C04255 | =L | D | | TB0113A | A008 | 2 | | 115-199 | |
| 0123 | 22 | GA | | 12-0 | 23-51-11 | TB0113Y | C018 | BJ | | D40808P | 23 | | | 115-199 | |
| 0124 | 22 | GA | | 1-0 | 23-51-11 | TB0113A | C007 | 2 | | TB0113A | C008 | 2 | | 115-199 | |
| 0125 | 22 | GA | | 1-0 | 23-51-11 | TB0113Y | C018 | BJ | | TB0113A | C008 | 2 | | 115-199 | |
| 0133 | 20 | GA | | 10-0 | 27-41-31 | C01010 | =L | D | | D40806P | 46 | | | 115-199 | |
| 0200 | 24 | GK | | 8-0 | 26-11-11 | C00774 | =L | D | | TB0112A | A024 | 2 | | 115-199 | |
| 0204 | 22 | GA | | 7-0 | 80-11-21 | C01511 | =L | D | | D41972J | 15 | | | 115-199 | |
| 0205 | 20 | GA | | 10-0 | 28-22-31 | C01051 | =L | D | | D40808P | 28 | | | 115-199 | |
| 0206 | 22 | GA | | 11-0 | 33-16-61 | C01308 | =L | D | | D40806P | 23 | | | 115-199 | |
| 0207 | 22 | GA | | 11-0 | 33-16-61 | C01201 | =L | D | | D40806P | 24 | | | 115-199 | |
| 0210 | 24 | GK | | 2-0 | 26-11-11 | TB0112A | C023 | 2 | | TB0112A | C024 | 2 | | 115-199 | |
| 0211 | 22 | GA | | 10-0 | 33-11-31 | C01214 | =L | D | | D40808P | 20 | | | 115-199 | |
| 0216 | 24 | GK | | 7-0 | 26-11-11 | TB0112A | C024 | 2 | | D40808P | 16 | | | 115-199 | |
| 0218 | 22 | GA | | 9-0 | 28-22-21 | C04132 | =L | D | | D40838J | 18 | | | 115-199 | |
| 0220 | 22 | GA | | 10-0 | 23-51-21 | C04257 | =L | D | | TB0113A | A009 | 2 | | 115-199 | |
| 0300 | 24 | GK | | 12-0 | 26-11-21 | TB0112A | C022 | 2 | | D40806P | 14 | | | 115-199 | |
| 0301 | 24 | GK | | 12-0 | 26-15-11 | TB0112A | C020 | 2 | | D40806P | 15 | | | 115-199 | |
| 0302 | 24 | GK | | 10-0 | 26-11-11 | C00783 | =L | D | | D40806P | 28 | | | 115-199 | |
| 0303 | 24 | GK | | 11-0 | 26-15-12 | C00796 | =L | D | | D40806P | 17 | | | 115-199 | |
| 0304 | 24 | GK | | 9-0 | 26-15-11 | C00776 | =L | D | | TB0112A | A020 | 2 | | 115-199 | |
| 0305 | 24 | GK | | 2-0 | 26-15-11 | TB0112A | C019 | 2 | | TB0112A | C020 | 2 | | 115-199 | |
| 0306 | 24 | GK | | 9-0 | 26-11-21 | C00775 | =L | D | | TB0112A | A022 | 2 | | 115-199 | |
| 0307 | 24 | GK | | 2-0 | 26-11-21 | TB0112A | C021 | 2 | | TB0112A | C022 | 2 | | 115-199 | |
| 0312 | 22 | GA | | 11-0 | 33-16-51 | C01307 | =L | D | | D40806P | 12 | | | 115-199 | |
| 0313 | 22 | GA | | 11-0 | 33-16-51 | C01200 | =L | D | | D40806P | 13 | | | 115-199 | |
| 0315 | 24 | GK | | 8-0 | 21-58-12 | C04085 | =L | D | * | D40838J | 5 | | | 115-199 | |
| 0400 | 22 | GA | | 10-0 | 30-21-11 | C01147 | =L | D | * | D40806P | 30 | | | 115-199 | |
| 0401 | 12 | HA | | 7-1 | 29-21-31 | C04216 | =L | D | | D40838J | 1 | | | 115-199 | |
| 0402 | 24 | GK | | 9-0 | 26-16-11 | C00772 | =L | D | | TB0112A | A018 | 2 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W0130

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|-------------|------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice | |
| W0134 | 286N0134 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT S(B) (continued) | | | | | | | | | | | |
| 0403 | 24 | | GK | | 2-0 | 26-16-11 | TB0112A | C017 | 2 | | TB0112A | C018 | 2 | | 115-199 | |
| 0405 | 22 | | GA | | 8-0 | 30-21-11 | C01147 | =L | D | * | D40838J | 9 | | | 115-199 | |
| 0406 | 22 | | GA | | 7-0 | 30-21-11 | C01148 | =L | D | * | D41972J | 14 | | | 115-199 | |
| 0407 | 22 | | GA | | 10-0 | 30-21-11 | C01148 | =L | D | * | D40808P | 5 | | | 115-199 | |
| 0408 | 16 | | GA | | 9-0 | 49-61-11 | C01390 | =L | D | | D40838J | 8 | | | 115-199 | |
| 0409 | 22 | | GA | | 8-0 | 80-11-11 | C01510 | =L | D | | D40838J | 7 | | | 115-199 | |
| 0410 | 22 | | GA | | 8-0 | 29-11-11 | C04023 | =L | D | | D40838J | 28 | | | 115-199 | |
| 0411 | 20 | | GA | | 7-0 | 29-21-31 | C04061 | =L | D | | D41972J | 11 | | | 115-199 | |
| 0412 | 16 | | GA | | 8-0 | 75-31-11 | C04113 | =L | D | | D40838J | 4 | | | 115-199 | |
| 0415 | 22 | | GA | | 9-0 | 28-22-21 | C04133 | =L | D | | D40838J | 14 | | | 115-199 | |
| 0416 | 24 | | GK | | 10-0 | 77-12-11 | C04151 | =L | D | | D40806P | 18 | | | 115-199 | |
| 0418 | 20 | | GA | | 8-0 | 28-25-21 | C04175 | =L | D | | D40838J | 16 | | | 115-199 | |
| 0419 | 24 | | GK | | 7-0 | 26-16-11 | TB0112A | C018 | 2 | | D40808P | 10 | | | 115-199 | |
| 0420 | 22 | | GA | | 8-0 | 21-58-12 | C04085 | =L | D | * | D40838J | 17 | | | 115-199 | |
| 0425 | 24 | | GK | | 11-0 | 26-16-11 | C00788 | =L | D | | D40806P | 26 | | | 115-199 | |
| W0136 | 286N0136 | | | | P11 MODULE WIRING, CB LOAD SIDE - CAT C | | | | | | | | | | | |
| 0001 | 20 | | GA | | 6-0 | 22-11-31 | C00515 | =L | D | | D40626J | 1 | | | 115-199 | |
| 0003 | 20 | | GA | | 6-0 | 22-11-32 | C00524 | =L | D | | D40626J | 3 | | | 115-199 | |
| 0009 | 22 | | GA | | 6-0 | 27-48-21 | C01525 | =L | D | | D40626J | 9 | | | 115-199 | |
| 0010 | 22 | | GA | | 6-0 | 34-33-31 | C00602 | =L | D | | D40626J | 4 | | | 115-199 | |
| 0011 | 22 | | GA | | 6-0 | 34-21-31 | C00613 | =L | D | | D40626J | 5 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11
Section W0130
Page 9 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity | | | | | | | | |
|------------|-------------|---|-------|----------|-------------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0200 | 286N0200 | FLIGHT DECK OVERHEAD LIGHT, CAPT. CAT S2. | | | | | | | | | | | |
| 0001 | 22 | GA | 4-0 | 33-14-11 | D41280J | 1 | | | L00277 | =P | C | | 001-099 |
| 0002 | 22 | GA | 4-0 | 33-14-11 | D41280J | 2 | | | L00277 | =G | C | | 001-099 |
| 0003 | 22 | GA | 3-0 | 33-11-31 | D41280J | 5 | | | L00275 | =P | C | | 001-099 |
| 0004 | 22 | GA | 3-0 | 33-11-31 | D41280J | 6 | | | L00275 | =G | C | | 001-099 |
| 0005 | 22 | GA | 4-0 | 33-11-31 | D41280J | 7 | | | M10549 | GND | C | | 001-099 |
| 0006 | 22 | GA | 4-0 | 33-11-31 | D41280J | 8 | | | M10549 | PWR | C | | 001-099 |
| 0007 | 22 | GA | 4-0 | 33-51-12 | R10381 | =P | \$ | | D05262 | 1 | VG | | 001-099 |
| 0008 | 22 | GA | 4-0 | 33-51-12 | D41280J | 10 | | | D05264 | 1 | VY | | 001-099 |
| 0009 | 22 | GA | 2-0 | 33-51-12 | R10381 | =G | \$ | | D41280J | 9 | | | 001-099 |
| C-A | | | 0-0 | 33-11-21 | D41280J | 4 | | | L00443 | W-A | | | 001-099 |
| C-B | | | 0-0 | 33-11-21 | D41280J | 3 | | | L00443 | W-B | | | 001-099 |
| W0202 | 286N0202 | FLIGHT DECK OVERHEAD LIGHT, CAPT. CAT S2. | | | | | | | | | | | |
| 0001 | 22 | GA | 4-0 | 33-14-11 | D41282J | 1 | | | L00278 | =P | C | | 001-099 |
| 0002 | 22 | GA | 4-0 | 33-14-11 | D41282J | 2 | | | L00278 | =G | C | | 001-099 |
| 0003 | 22 | GA | 3-0 | 33-11-31 | D41282J | 5 | | | L00276 | =P | C | | 001-099 |
| 0004 | 22 | GA | 3-0 | 33-11-31 | D41282J | 6 | | | L00276 | =G | C | | 001-099 |
| B-A | | | 0-0 | 33-11-21 | D41282J | 3 | | | L00444 | W-A | | | 001-099 |
| B-B | | | 0-0 | 33-11-21 | D41282J | 4 | | | L00444 | W-B | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0200

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|----------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0443 | 286N0443 | | | CONTROL COLUMN-CAPT | | | | | | | | | | | |
| 0000B | 24 | | GA | | 0-0 | SPARE | QD0002 | | GS | | TB0065X | CAP | Y | | ALL |
| 0000G | 24 | | GA | | 0-0 | SPARE | QD0004 | | GS | | TB0065X | CAP | Y | | ALL |
| 0000K | 24 | | GA | | 0-0 | 27-41-11 | QD0005 | | GS | | TB0065Y | C005 | BJ | | ALL |
| 0000KY | 24 | | GA | | 0-0 | 22-11-12 | QD0019 | | GS | | TB0065X | A002 | BJ | | ALL |
| 0000N | 24 | | GA | | 0-0 | 27-41-11 | QD0008 | | GS | | TB0065Y | C006 | BJ | | ALL |
| 0000O | 24 | | GA | | 0-0 | 27-41-11 | QD0007 | | GS | | TB0065Y | A007 | BJ | | ALL |
| 0000P | 24 | | GA | | 0-0 | 23-51-11 | QD0009 | | GS | | TB0065Y | A008 | BJ | | ALL |
| 0000R | 24 | | GA | | 0-0 | SPARE | QD0001 | | GS | | TB0065X | CAP | Y | | ALL |
| 0000RG | 24 | | GA | | 0-0 | 22-11-32 | QD0020 | | GS | | TB0065X | D004 | BJ | | ALL |
| 0000RK | 24 | | GA | | 0-0 | 23-51-11 | QD0021 | | GS | | TB0065Y | A008 | BJ | | ALL |
| 0000V | 24 | | GA | | 0-0 | 27-41-11 | QD0006 | | GS | | TB0065Y | A005 | BJ | | ALL |
| 0000WB | 24 | | GA | | 0-0 | 22-11-22 | QD0011 | | GS | | TB0065X | B003 | BJ | | ALL |
| 0000WG | 24 | | GA | | 0-0 | 22-11-12 | QD0013 | | GS | | TB0065X | C002 | BJ | | ALL |
| 0000WK | 24 | | GA | | 0-0 | 22-11-22 | QD0014 | | GS | | TB0065X | C004 | BJ | | ALL |
| 0000WN | 24 | | GA | | 0-0 | 22-11-32 | QD0017 | | GS | | TB0065X | B004 | BJ | | ALL |
| 0000WO | 24 | | GA | | 0-0 | 23-51-11 | QD0016 | | GS | | TB0065X | A009 | BJ | | ALL |
| 0000WP | 24 | | GA | | 0-0 | 22-11-12 | QD0018 | | GS | | TB0065X | B002 | BJ | | ALL |
| 0000WR | 24 | | GA | | 0-0 | 23-51-11 | QD0010 | | GS | | TB0065X | C009 | BJ | | ALL |
| 0000WV | 24 | | GA | | 0-0 | 27-41-11 | QD0015 | | GS | | TB0065Y | A006 | BJ | | ALL |
| 0000WY | 24 | | GA | | 0-0 | 22-11-12 | QD0012 | | GS | | TB0065X | D002 | BJ | | ALL |
| 0000Y | 24 | | GA | | 0-0 | SPARE | QD0003 | | GS | | TB0065X | CAP | Y | | ALL |
| W0445 | 286N0445 | | | CONTROL COLUMN-F/O | | | | | | | | | | | |
| 0000B | 24 | | GA | | 0-0 | SPARE | QD0040 | | GS | | TB0065X | CAP | Y | | ALL |
| 0000G | 24 | | GA | | 0-0 | SPARE | QD0042 | | GS | | TB0065X | CAP | Y | | ALL |
| 0000K | 24 | | GA | | 0-0 | 27-41-21 | QD0022 | | GS | | TB0065Y | C005 | BJ | | ALL |
| 0000KY | 24 | | GA | | 0-0 | 22-11-12 | QD0036 | | GS | | TB0065X | C001 | BJ | | ALL |
| 0000N | 24 | | GA | | 0-0 | 27-41-21 | QD0025 | | GS | | TB0065Y | C006 | BJ | | ALL |
| 0000O | 24 | | GA | | 0-0 | 27-41-21 | QD0024 | | GS | | TB0065Y | A007 | BJ | | ALL |
| 0000P | 24 | | GA | | 0-0 | 23-51-21 | QD0026 | | GS | | TB0065Y | C008 | BJ | | ALL |
| 0000R | 24 | | GA | | 0-0 | SPARE | QD0039 | | GS | | TB0065X | CAP | Y | | ALL |
| 0000RG | 24 | | GA | | 0-0 | 22-11-32 | QD0037 | | GS | | TB0065X | A004 | BJ | | ALL |
| 0000RK | 24 | | GA | | 0-0 | 23-51-21 | QD0038 | | GS | | TB0065Y | C008 | BJ | | ALL |
| 0000V | 24 | | GA | | 0-0 | 27-41-21 | QD0023 | | GS | | TB0065Y | A005 | BJ | | ALL |
| 0000WB | 24 | | GA | | 0-0 | 22-11-22 | QD0028 | | GS | | TB0065X | C003 | BJ | | ALL |
| 0000WG | 24 | | GA | | 0-0 | 22-11-12 | QD0030 | | GS | | TB0065X | D001 | BJ | | ALL |
| 0000WK | 24 | | GA | | 0-0 | 22-11-22 | QD0031 | | GS | | TB0065X | A003 | BJ | | ALL |
| 0000WN | 24 | | GA | | 0-0 | 22-11-32 | QD0034 | | GS | | TB0065X | D003 | BJ | | ALL |
| 0000WO | 24 | | GA | | 0-0 | 23-51-21 | QD0033 | | GS | | TB0065X | A010 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0440

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0445 | 286N0445 | | | CONTROL COLUMN-F/O (continued) | | | | | | | | | | | |
| 0000WP | 24 | | GA | | 0-0 | 22-11-12 | QD0035 | | GS | | TB0065X | B001 | BJ | | ALL |
| 0000WR | 24 | | GA | | 0-0 | 23-51-21 | QD0027 | | GS | | TB0065X | C010 | BJ | | ALL |
| 0000WV | 24 | | GA | | 0-0 | 27-41-21 | QD0032 | | GS | | TB0065Y | A006 | BJ | | ALL |
| 0000WY | 24 | | GA | | 0-0 | 22-11-12 | QD0029 | | GS | | TB0065X | A001 | BJ | | ALL |
| 0000Y | 24 | | GA | | 0-0 | SPARE | QD0041 | | GS | | TB0065X | CAP | Y | | ALL |
| W0447 | 286N0447 | | | E3-3 TO CONTROL POSITION SENSORS | | | | | | | | | | | |
| 0001 | 24 | | GK | | 47-0 | 31-31-51 | D41145P | | 1 | | D01493 | 2 | | | 001-099 |
| 0002 | 24 | | GK | | 42-0 | 31-31-51 | D41145P | | 4 | | D01495 | 2 | | | 001-099 |
| 0003 | 24 | | GK | | 47-0 | 31-31-51 | D41145P | | 7 | | D01491 | 2 | | | 001-099 |
| 0004 | 20 | | GA | | 5-0 | 31-31-51 | D01493 | | 1 | | GD00159 | AC.. | E | *1 | 001-099 |
| 0005 | 20 | | GA | | 5-0 | 31-31-51 | D01493 | | 3 | | GD00159 | AC.. | E | *1 | 001-099 |
| 0006 | 20 | | GA | | 4-0 | 31-31-51 | D01495 | | 1 | | GD00159 | AC.. | E | *2 | 001-099 |
| 0007 | 20 | | GA | | 4-0 | 31-31-51 | D01495 | | 3 | | GD00159 | AC.. | E | *2 | 001-099 |
| 0008 | 20 | | GA | | 5-0 | 31-31-51 | D01491 | | 1 | | GD00159 | AC.. | E | *3 | 001-099 |
| 0009 | 20 | | GA | | 5-0 | 31-31-51 | D01491 | | 3 | | GD00159 | AC.. | E | *3 | 001-099 |
| 2001B | 24 | | GL | AA | 47-0 | 31-31-51 | D41145P | | 3 | | D01493 | 5 | | | 001-099 |
| 2001R | 24 | | GL | AA | 0-0 | 31-31-51 | D41145P | | 2 | | D01493 | 4 | | | 001-099 |
| 2002B | 24 | | GL | AB | 42-0 | 31-31-51 | D41145P | | 6 | | D01495 | 5 | | | 001-099 |
| 2002R | 24 | | GL | AB | 0-0 | 31-31-51 | D41145P | | 5 | | D01495 | 4 | | | 001-099 |
| 2003B | 24 | | GL | AC | 47-0 | 31-31-51 | D41145P | | 9 | | D01491 | 5 | | | 001-099 |
| 2003R | 24 | | GL | AC | 0-0 | 31-31-51 | D41145P | | 8 | | D01491 | 4 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0440

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0502 | 286N0502 | | | | FLIGHT DECK COMPARTMENT DOOR LOCK | | | | | | | | | | |
| 0001 | 20 | | GA | | 3-0 | 33-22-11 | D41106P | 3 | | | SM00001 | | 9 | | ALL |
| 0002 | 20 | | GA | | 3-0 | 33-22-11 | D41106P | 4 | | | SM00002 | | 9 | | ALL |
| 0003 | 20 | | GA | | 5-0 | 52-51-11 | D41106P | 1 | | | D07162 | 1 | VY | | ALL |
| 0004 | 20 | | GA | | 4-0 | 52-51-11 | D41106P | 2 | | | D07160 | 1 | VG | | ALL |
| B-GA | | | | | 0-0 | 33-22-11 | SM00002 | | 9 | | S10165B | | BLU | | ALL |
| B-PA | | | | | 0-0 | 33-22-11 | SM00001 | | 9 | | S10165B | | RED | | ALL |
| W0504 | 286N0504 | | | | P21 FWD ATTENDANT PNL | | | | | | | | | | |
| 0001 | 20 | | 1E | | 1-2 | 33-22-11 | D02458 | 1 | | | SM00001 | | WI | | 001-099 |
| 0001 | 20 | | 1E | | 2-0 | 33-22-11 | D02458 | 1 | | | SM00001 | | WI | | 115-199 |
| 0002 | 22 | | 1E | | 1-2 | 33-22-11 | D02458 | 2 | | | SM00002 | | WI | | 001-099 |
| 0002 | 22 | | 1E | | 2-0 | 33-22-11 | D02458 | 2 | | | SM00002 | | WI | | 115-199 |
| 0003 | 22 | | 1E | | 1-2 | 33-22-11 | D02458 | 3 | | | SM00003 | | WI | | 001-099 |
| 0003 | 22 | | 1E | | 2-0 | 33-22-11 | D02458 | 3 | | | SM00003 | | WI | | 115-199 |
| 0004 | 20 | | 1E | | 1-2 | 33-22-11 | D02458 | 4 | | | SM00004 | | WI | | 001-099 |
| 0004 | 20 | | 1E | | 2-0 | 33-22-11 | D02458 | 4 | | | SM00004 | | WI | | 115-199 |
| 0005 | 22 | | 1E | | 2-6 | 33-22-11 | D02458 | 5 | | | S10302 | | C1 | \$ | * 001-099 |
| 0005 | 22 | | 1E | | 3-0 | 33-22-11 | D02458 | 5 | | | S10302 | | C1 | \$ | * 115-199 |
| 0006 | 22 | | 1E | | 2-6 | 33-22-11 | D02458 | 6 | | | S10302 | | 2 | \$ | * 001-099 |
| 0006 | 22 | | 1E | | 3-0 | 33-22-11 | D02458 | 6 | | | S10302 | | 2 | \$ | * 115-199 |
| 0007 | 22 | | 1E | | 2-6 | 33-22-11 | D02458 | 7 | | | S10302 | | 6 | \$ | 001-099 |
| 0007 | 22 | | 1E | | 3-0 | 33-22-11 | D02458 | 7 | | | S10302 | | 6 | \$ | 115-199 |
| 0008 | 22 | | 1E | | 2-6 | 33-22-11 | D02458 | 8 | | | S10302 | | 1 | \$ | 001-099 |
| 0008 | 22 | | 1E | | 3-0 | 33-22-11 | D02458 | 8 | | | S10302 | | 1 | \$ | 115-199 |
| 0009 | 22 | | 1E | | 2-3 | 24-51-51 | D02458 | 9 | | | S10296 | | NO | Z1 | 001-099 |
| 0009 | 22 | | 1E | | 3-0 | 24-51-51 | D02458 | 9 | | | S10296 | | NO | Z1 | 115-199 |
| 0010 | 22 | | 1E | | 2-3 | 24-51-51 | D02458 | 10 | | | S10296 | | C | Z1 | 001-099 |
| 0010 | 22 | | 1E | | 3-0 | 24-51-51 | D02458 | 10 | | | S10296 | | C | Z1 | 115-199 |
| 0011 | 22 | | 1E | | 2-3 | 24-51-51 | D02458 | 11 | | | S10296 | | + | Z1 | 001-099 |
| 0011 | 20 | | 1E | | 3-0 | 24-51-51 | D02458 | 11 | | | S10296 | | + | Z1 | 115-199 |
| 0012 | 22 | | 1E | | 2-3 | 24-51-51 | D02458 | 12 | | | S10296 | | - | Z1 | 001-099 |
| 0012 | 20 | | 1E | | 3-0 | 24-51-51 | SM00005 | | WI | | S10296 | | - | Z1 | 115-199 |
| 0013 | 24 | | 1E | | 2-8 | 33-21-11 | D02458 | 13 | | | S10298 | | C1 | \$ | 001-099 |
| 0013 | 24 | | 1E | | 3-0 | 33-21-11 | D02458 | 13 | | | S10298 | | C1 | \$ | 115-199 |
| 0014 | 24 | | 1E | | 2-8 | 33-21-11 | D02458 | 14 | | | S10298 | | 10 | \$ | * 001-099 |
| 0014 | 24 | | 1E | | 3-0 | 33-21-11 | D02458 | 14 | | | S10298 | | 10 | \$ | * 115-199 |
| 0015 | 24 | | 1E | | 2-8 | 33-21-11 | D02458 | 15 | | | S10298 | | 4 | \$ | 001-099 |
| 0015 | 24 | | 1E | | 3-0 | 33-21-11 | D02458 | 15 | | | S10298 | | 4 | \$ | 115-199 |
| 0016 | 22 | | 1E | | 2-8 | 33-21-51 | D02458 | 16 | | | S10298 | | 8 | \$ | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0500

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|-----|-----------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0504 | 286N0504 | | | | P21 FWD ATTENDANT PNL (continued) | | | | | | | | | | | | |
| 0016 | 22 | | 1E | | 3-0 | 33-21-51 | D02458 | 16 | | | | S10298 | 8 | \$ | | 115-199 | |
| 0017 | 22 | | 1E | | 2-8 | 33-21-51 | D02458 | 17 | | | | S10298 | C2 | \$ | | 001-099 | |
| 0017 | 22 | | 1E | | 3-0 | 33-21-11 | D02458 | 17 | | | | S10298 | C2 | \$ | | 115-199 | |
| 0018 | 24 | | 1E | | 2-4 | 33-21-31 | D02458 | 18 | | | | S10299 | 2 | \$ | * | 001-099 | |
| 0018 | 24 | | 1E | | 3-0 | 33-21-31 | D02458 | 18 | | | | S10299 | 2 | \$ | * | 115-199 | |
| 0019 | 24 | | 1E | | 2-4 | 33-21-31 | D02458 | 19 | | | | S10299 | 5 | \$ | | 001-099 | |
| 0019 | 24 | | 1E | | 4-0 | 33-21-31 | D02458 | 19 | | | | S10299 | 5 | \$ | | 115-199 | |
| 0020 | 24 | | 1E | | 2-4 | 33-21-31 | D02458 | 20 | | | | S10299 | C1 | \$ | | 001-099 | |
| 0020 | 24 | | 1E | | 4-0 | 33-21-31 | D02458 | 20 | | | | S10299 | C1 | \$ | | 115-199 | |
| 0021 | 22 | | 1E | | 3-0 | 33-27-11 | D02458 | 35 | | | | S10369 | 3 | \$ | | 115-199 | |
| 0022 | 22 | | 1E | | 3-0 | 33-27-11 | SM00006 | | | WI | | S10369 | 6 | \$ | | 115-199 | |
| 0023 | 22 | | 1E | | 3-0 | 33-27-11 | SM00006 | | | WI | | S10369 | 5 | \$ | | 115-199 | |
| 0024 | 22 | | 1E | | 3-0 | 33-27-11 | D02458 | 36 | | | | S10369 | 4 | \$ | | 115-199 | |
| 0025 | 22 | | 1E | | 2-0 | 33-27-11 | SM00006 | | | WI | | D02458 | 37 | | | 115-199 | |
| 0026 | 22 | | 1E | | 1-0 | 33-27-11 | S10369 | C1 | \$ | | * | S10369 | C2 | \$ | | 115-199 | |
| 0027 | 22 | | 1E | | 2-0 | 33-27-11 | S10302 | C2 | \$ | | * | S10369 | C1 | \$ | * | 115-199 | |
| 0029 | 22 | | 1E | | 3-0 | 23-34-16 | D02458 | 29 | | | | S10179 | B | \$ | | 115-199 | |
| 0030 | 22 | | 1E | | 3-0 | 23-34-16 | D02458 | 30 | | | | S10179 | D | \$ | | 115-199 | |
| 0031 | 22 | | 1E | | 1-0 | 23-34-16 | S10179 | 6 | \$ | | | S10179 | 8 | \$ | * | 115-199 | |
| 0032 | 22 | | 1E | | 1-0 | 23-34-16 | S10179 | 8 | \$ | | * | S10179 | 4 | \$ | * | 115-199 | |
| 0033 | 22 | | 1E | | 1-7 | 33-22-11 | SM00003 | | | WI | | S10301 | NO | Z1 | | 001-099 | |
| 0033 | 22 | | 1E | | 2-0 | 33-22-11 | SM00003 | | | WI | | S10301 | NO | Z1 | | 115-199 | |
| 0034 | 20 | | 1E | | 2-2 | 33-21-11 | D02458 | 34 | | | | GDX0001 | ST.. | H | | 001-099 | |
| 0034 | 20 | | 1E | | 3-0 | 33-21-11 | D02458 | 34 | | | | GDX0001 | ST.. | H | | 115-199 | |
| 0035 | 22 | | 1E | | 1-0 | 23-34-16 | S10179 | 3 | \$ | | * | S10179 | 4 | \$ | * | 115-199 | |
| 0036 | 22 | | 1E | | 3-0 | 23-34-16 | D02458 | 21 | | | | S10179 | F | \$ | | 115-199 | |
| 0037 | 22 | | 1E | | 3-0 | 23-34-16 | D02458 | 12 | | | | S10179 | E | \$ | | 115-199 | |
| 0038 | 22 | | 1E | | 3-0 | 33-51-11 | D02458 | 38 | | | | S10297 | 2C | Z1 | | ALL | |
| 0039 | 22 | | 1E | | 3-0 | 33-51-11 | D02458 | 39 | | | | S10297 | 1C | Z1 | | ALL | |
| 0040 | 22 | | 1E | | 3-0 | 33-51-11 | D02458 | 40 | | | | S10297 | 3C | Z1 | | ALL | |
| 0041 | 20 | | 1E | | 1-2 | 33-51-11 | D02458 | 41 | | | | SM00005 | | WI | | 001-099 | |
| 0041 | 20 | | 1E | | 2-0 | 33-51-11 | D02458 | 41 | | | | SM00005 | | WI | | 115-199 | |
| 0042 | 22 | | 1E | | 3-0 | 23-34-16 | D02458 | 22 | | | | S10179 | 3 | \$ | * | 115-199 | |
| 0043 | 22 | | 1E | | 3-0 | 23-34-15 | S10479 | 3 | \$ | | | SM00005 | | WI | | 115-199 | |
| 0045 | 22 | | 1E | | 2-4 | 33-51-11 | SM00005 | | | WI | | S10297 | 2NO | Z1 | | 001-099 | |
| 0045 | 20 | | 1E | | 2-0 | 33-51-11 | SM00005 | | | WI | | S10297 | 2NO | Z1 | | 115-199 | |
| 0051 | 22 | | 1E | | 1-8 | 33-22-11 | S10300 | + | Z1 | | | SM00002 | | WI | | 001-099 | |
| 0051 | 22 | | 1E | | 2-0 | 33-22-11 | S10300 | + | Z1 | | | SM00002 | | WI | | 115-199 | |
| 0052 | 22 | | 1E | | 1-8 | 33-22-11 | S10300 | - | Z1 | | | SM00004 | | WI | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W0500

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-----------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W0504 | 286N0504 | | | | P21 FWD ATTENDANT PNL (continued) | | | | | | | | | | | |
| 0052 | 20 | | 1E | | 2-0 | 33-22-11 | S10300 | | - | Z1 | | SM00004 | | WI | | 115-199 |
| 0053 | 22 | | 1E | | 1-7 | 33-22-11 | SM00004 | | | WI | | S10301 | - | Z1 | | 001-099 |
| 0053 | 20 | | 1E | | 2-0 | 33-22-11 | SM00004 | | | WI | | S10301 | - | Z1 | | 115-199 |
| 0055 | 22 | | 1E | | 1-7 | 33-22-11 | S10301 | | + | Z1 | | SM00003 | | WI | | 001-099 |
| 0055 | 22 | | 1E | | 2-0 | 33-22-11 | S10301 | | + | Z1 | | SM00003 | | WI | | 115-199 |
| 0056 | 20 | | 1E | | 3-0 | 23-34-16 | D02458 | | 31 | | | S10179 | C | \$ | * | 115-199 |
| 0057 | 20 | | 1E | | 2-0 | 23-34-16 | S10179 | | A | \$ | | S10179 | C | \$ | * | 115-199 |
| 0058 | 24 | | 1E | | 0-7 | 33-21-31 | S10299 | | 3 | \$ | | S10299 | 2 | \$ | * | 001-099 |
| 0058 | 24 | | 1E | | 1-0 | 33-21-31 | S10299 | | 3 | \$ | | S10299 | 2 | \$ | * | 115-199 |
| 0059 | 24 | | 1E | | 2-4 | 33-21-31 | S10299 | | C2 | \$ | | D02458 | 24 | | | 001-099 |
| 0059 | 24 | | 1E | | 4-0 | 33-21-31 | S10299 | | C2 | \$ | | D02458 | 24 | | | 115-199 |
| 0060 | 22 | | 1E | | 0-7 | 33-22-11 | S10302 | | 3 | \$ | | S10302 | 2 | \$ | * | 001-099 |
| 0060 | 22 | | 1E | | 2-0 | 33-22-11 | S10302 | | 3 | \$ | | S10302 | 2 | \$ | * | 115-199 |
| 0061 | 22 | | 1E | | 0-7 | 33-22-11 | S10302 | | C2 | \$ | | S10302 | C1 | \$ | * | 001-099 |
| 0061 | 22 | | 1E | | 2-0 | 33-22-11 | S10302 | | C2 | \$ | * | S10302 | C1 | \$ | * | 115-199 |
| 0062 | 24 | | 1E | | 0-7 | 33-21-11 | S10298 | | 9 | \$ | | S10298 | 10 | \$ | * | 001-099 |
| 0062 | 24 | | 1E | | 1-0 | 33-21-11 | S10298 | | 9 | \$ | | S10298 | 10 | \$ | * | 115-199 |
| 0063 | 22 | | 1E | | 0-7 | 33-51-11 | S10297 | | 1NO | Z1 | | S10297 | + | Z1 | | 001-099 |
| 0063 | 22 | | 1E | | 1-0 | 33-51-11 | S10297 | | 1NO | Z1 | | S10297 | + | Z1 | | 115-199 |
| 0064 | 22 | | 1E | | 2-4 | 33-51-11 | SM00005 | | | WI | | S10297 | - | Z1 | | 001-099 |
| 0064 | 20 | | 1E | | 2-0 | 33-51-11 | SM00005 | | | WI | | S10297 | - | Z1 | | 115-199 |
| 0065 | 22 | | 1E | | 2-4 | 33-51-11 | S10297 | | 3NC | Z1 | | SM00005 | | WI | | 001-099 |
| 0065 | 20 | | 1E | | 2-0 | 33-51-11 | S10297 | | 3NC | Z1 | | SM00005 | | WI | | 115-199 |
| 0066 | 22 | | 1E | | 1-7 | 33-22-11 | S10301 | | C | Z1 | | SM00001 | | WI | | 001-099 |
| 0066 | 22 | | 1E | | 2-0 | 33-22-11 | S10301 | | C | Z1 | | SM00001 | | WI | | 115-199 |
| 0101 | 22 | | 1E | | 1-8 | 33-22-11 | SM00001 | | | WI | | S10300 | C | Z1 | | 001-099 |
| 0101 | 22 | | 1E | | 2-0 | 33-22-11 | SM00001 | | | WI | | S10300 | C | Z1 | | 115-199 |
| 0102 | 22 | | 1E | | 1-8 | 33-22-11 | SM00002 | | | WI | | S10300 | NO | Z1 | | 001-099 |
| 0102 | 22 | | 1E | | 2-0 | 33-22-11 | SM00002 | | | WI | | S10300 | NO | Z1 | | 115-199 |
| 0103 | 22 | | 1E | | 2-5 | 23-34-15 | D02458 | | 32 | | | S10479 | C1 | \$ | | 001-099 |
| 0103 | 22 | | 1E | | 3-0 | 23-34-15 | D02458 | | 32 | | | S10479 | C1 | \$ | | 115-199 |
| 0104 | 22 | | 1E | | 2-5 | 23-34-15 | D02458 | | 33 | | | S10479 | 5 | \$ | * | 001-099 |
| 0104 | 22 | | 1E | | 3-0 | 23-34-15 | D02458 | | 33 | | | S10479 | 5 | \$ | * | 115-199 |
| 0105 | 22 | | 1E | | 2-5 | 23-34-15 | D02458 | | 23 | | | S10479 | C2 | \$ | | 001-099 |
| 0105 | 22 | | 1E | | 3-0 | 23-34-15 | D02458 | | 23 | | | S10479 | C2 | \$ | | 115-199 |
| 0108 | 22 | | 1E | | 2-5 | 23-34-15 | D02458 | | 25 | | | S10479 | 3 | \$ | | 001-099 |
| 0108 | 22 | | 1E | | 3-0 | 23-34-15 | D02458 | | 25 | | | SM00005 | | WI | | 115-199 |
| 0109 | 22 | | 1E | | 0-7 | 23-34-15 | S10479 | | 5 | \$ | * | S10479 | 6 | \$ | | 001-099 |
| 0109 | 22 | | 1E | | 1-0 | 23-34-15 | S10479 | | 5 | \$ | * | S10479 | 6 | \$ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0500

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------|-------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0504 | 286N0504 | | | P21 FWD ATTENDANT PNL (continued) | | | | | | | | | | | |
| 3026B | 22 | 1G | AA | | 3-0 | 23-34-16 | D02458 | 28 | | | S10179 | CCW | \$ | | 115-199 |
| 3026R | 22 | 1G | AA | | 0-0 | 23-34-16 | D02458 | 26 | | | S10179 | CW | \$ | | 115-199 |
| 3026Y | 22 | 1G | AA | | 0-0 | 23-34-16 | D02458 | 27 | | | S10179 | ARM | \$ | | 115-199 |
| W0506 | 286N0506 | | | P23 MID ATTENDANT PNL | | | | | | | | | | | |
| 0001 | 22 | 1E | | | 1-3 | 33-22-12 | D04634 | 1 | | | S10159 | C | Z1 | | 001-099 |
| 0002 | 22 | 1E | | | 1-4 | 33-22-12 | D04634 | 2 | | | SM00001 | | WI | | 001-099 |
| 0003 | 22 | 1E | | | 1-3 | 33-22-12 | D04634 | 3 | | | S10159 | - | Z1 | | 001-099 |
| 0004 | 22 | 1E | | | 0-10 | 33-22-12 | S10159 | + | Z1 | | SM00001 | | WI | | 001-099 |
| 0005 | 22 | 1E | | | 0-10 | 33-22-12 | S10159 | NO | Z1 | | SM00001 | | WI | | 001-099 |
| W0507 | 286N0507 | | | WINDSCREEN DR 4 | | | | | | | | | | | |
| 4252B | 22 | GW | AA | | 8-0 | 23-42-11 | D41893P | 3 | | | D00767 | 3 | | | ALL |
| 4252G | 22 | GW | AA | | 0-0 | 23-42-11 | D41893P | 5 | | | D00767 | 5 | | | ALL |
| 4252R | 22 | GW | AA | | 0-0 | 23-42-11 | D41893P | 1 | | | D00767 | 1 | | | ALL |
| 4252Y | 22 | GW | AA | | 0-0 | 23-42-11 | D41893P | 4 | | | D00767 | 4 | | | ALL |
| 4252Z | | | AA | | 0-0 | 23-42-11 | D41893P | 2 | | | D00767 | 2 | | | ALL |
| W0509 | 286N0509 | | | WINDSCREEN DR 1 | | | | | | | | | | | |
| 4251B | 22 | GW | AA | | 7-10 | 23-42-11 | D00939 | 3 | | | D00945 | 3 | | | 001-099 |
| 4251G | 22 | GW | AA | | 0-0 | 23-42-11 | D00939 | 5 | | | D00945 | 5 | | | 001-099 |
| 4251R | 22 | GW | AA | | 0-0 | 23-42-11 | D00939 | 1 | | | D00945 | 1 | | | 001-099 |
| 4251Y | 22 | GW | AA | | 0-0 | 23-42-11 | D00939 | 4 | | | D00945 | 4 | | | 001-099 |
| 4251Z | | | AA | | 0-0 | 23-42-11 | D00939 | 2 | | | D00945 | 2 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0500

Page 4 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------|-------|--------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0510 | 286N0510 | | | | | P22 AFT ATTENDANT PANEL | | | | | | | | | |
| 0001 | 22 | | 1E | | 2-0 | 33-22-14 | D04616 | 1 | | | SM00001 | | WI | | 001-099 |
| 0001 | 22 | | 1E | | 2-0 | 33-22-14 | SM00001 | | WI | | S10167 | NO | Z1 | | 115-199 |
| 0002 | 22 | | 1E | | 2-0 | 33-22-14 | D04616 | 2 | | | SM00002 | | WI | | 001-099 |
| 0002 | 22 | | 1E | | 2-0 | 33-22-14 | SM00001 | | WI | | S10167 | + | Z1 | | 115-199 |
| 0003 | 20 | | 1E | | 2-0 | 33-22-14 | D04616 | 3 | | | SM00003 | | WI | | 001-099 |
| 0003 | 20 | | 1E | | 2-0 | 33-22-14 | SM00002 | | WI | | S10167 | - | Z1 | | 115-199 |
| 0004 | 22 | | 1E | | 2-0 | 33-22-14 | D04616 | 4 | | | SM00004 | | WI | | 001-099 |
| 0004 | 22 | | 1E | | 2-0 | 33-22-14 | SM00003 | | WI | | S10336 | NO | Z1 | | 115-199 |
| 0005 | 22 | | 1E | | 1-0 | 33-22-14 | SM00001 | | WI | | S10167 | C | Z1 | | 001-099 |
| 0005 | 22 | | 1E | | 2-0 | 33-22-14 | SM00003 | | WI | | S10336 | + | Z1 | | 115-199 |
| 0006 | 22 | | 1E | | 1-0 | 33-22-14 | SM00002 | | WI | | S10167 | NO | Z1 | | 001-099 |
| 0006 | 20 | | 1E | | 2-0 | 33-22-14 | SM00002 | | WI | | S10336 | - | Z1 | | 115-199 |
| 0007 | 22 | | 1E | | 1-0 | 33-22-14 | SM00002 | | WI | | S10167 | + | Z1 | | 001-099 |
| 0007 | 22 | | 1E | | 2-0 | 33-27-31 | D04616 | 6 | | | S10368 | 3 | \$ | | 115-199 |
| 0008 | 22 | | 1E | | 1-0 | 33-22-14 | SM00003 | | WI | | S10167 | - | Z1 | | 001-099 |
| 0008 | 22 | | 1E | | 2-0 | 33-27-31 | SM00004 | | WI | | S10368 | 6 | \$ | | 115-199 |
| 0009 | 22 | | 1E | | 2-0 | 33-22-14 | SM00001 | | WI | | S10336 | C | Z1 | | 001-099 |
| 0009 | 22 | | 1E | | 2-0 | 33-27-31 | SM00004 | | WI | | S10368 | 5 | \$ | | 115-199 |
| 0010 | 22 | | 1E | | 2-0 | 33-22-14 | SM00003 | | WI | | S10336 | - | Z1 | | 001-099 |
| 0010 | 22 | | 1E | | 2-0 | 33-27-31 | D04616 | 8 | | | S10368 | 4 | \$ | | 115-199 |
| 0011 | 22 | | 1E | | 2-0 | 33-22-14 | SM00004 | | WI | | S10336 | NO | Z1 | | 001-099 |
| 0011 | 22 | | 1E | | 2-0 | 33-22-14 | D04616 | 2 | | | SM00001 | | WI | | 115-199 |
| 0012 | 22 | | 1E | | 2-0 | 33-22-14 | SM00004 | | WI | | S10336 | + | Z1 | | 001-099 |
| 0012 | 20 | | 1E | | 2-0 | 33-22-14 | D04616 | 3 | | | SM00002 | | WI | | 115-199 |
| 0013 | 22 | | 1E | | 2-0 | 33-22-14 | D04616 | 4 | | | SM00003 | | WI | | 115-199 |
| 0014 | 22 | | 1E | | 2-0 | 33-27-31 | D04616 | 7 | | | SM00004 | | WI | | 115-199 |
| 0015 | 22 | | 1E | | 2-0 | 33-27-31 | S10368 | C2 | \$ | | SM00005 | | WI | | 115-199 |
| 0016 | 22 | | 1E | | 2-0 | 33-27-31 | S10368 | C1 | \$ | | SM00005 | | WI | | 115-199 |
| 0017 | 22 | | 1E | | 2-0 | 33-27-31 | D04616 | 5 | | | SM00005 | | WI | | 115-199 |
| 0018 | 22 | | 1E | | 2-0 | 33-22-14 | S10336 | C | Z1 | | SM00006 | | WI | | 115-199 |
| 0019 | 22 | | 1E | | 2-0 | 33-22-14 | D04616 | 1 | | | SM00006 | | WI | | 115-199 |
| 0020 | 22 | | 1E | | 2-0 | 33-22-14 | S10167 | C | Z1 | | SM00006 | | WI | | 115-199 |
| 0021 | 20 | | 1E | | 2-0 | 33-22-14 | D04616 | 9 | | | GDX0001 | ST.. | H | | 115-199 |
| W0511 | 286N0511 | | | | | DR 2 PANEL ASSY - CHIME | | | | | | | | | |
| 0001 | 22 | | GA | | 6-0 | 33-25-12 | D05091 | 1 | | | B10101 | HI | C | * | 115-199 |
| 0002 | 22 | | GA | | 6-0 | 33-25-12 | D05091 | 2 | | | B10101 | HI | C | * | 115-199 |
| 0003 | 22 | | GA | | 6-0 | 23-42-12 | D05091 | 3 | | | B10101 | 28V | C | | 115-199 |
| 0004 | 20 | | GA | | 6-0 | 23-42-12 | D05091 | 4 | | | B10101 | GND | C | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0510

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|---------|------|--------|----|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0511 | 286N0511 | | | | DR 2 PANEL ASSY - CHIME (continued) | | | | | | | | | | | | |
| 0005 | 24 | | GK | | 6-0 | 23-42-12 | | D05091 | | 5 | | B10101 | H/L | C | | 115-199 | |
| W0512 | 286N0512 | | | | PASSENGER SERVICE UNIT-FULL (UNDER BIN) | | | | | | | | | | | | |
| 0001WY | 18 | | GA | | 4-0 | 33-24-31 | | D03440 | | 1 | | L00447 | FSB | AB | | 001-099 | |
| 0001Y | 20 | | GA | | 3-7 | 33-24-31 | | D03440 | | 1 | | L00447 | FSB | AB | | 115-199 | |
| 0002RY | 22 | | GA | | 2-7 | 33-25-31 | | D03440 | | 2 | | S10272 | | 6 | Z2 | 115-199 | |
| 0002WV | 22 | | GA | | 4-0 | 33-25-31 | | D03440 | | 2 | | S10271 | | 3 | Z1 | 001-099 | |
| 0003RL | 22 | | GA | | 2-7 | 33-25-31 | | D03440 | | 3 | | S10272 | | 3 | Z2 | 115-199 | |
| 0003WG | 22 | | GA | | 3-0 | 33-25-31 | | D03440 | | 3 | | S10272 | | 3 | Z2 | 001-099 | |
| 0004RN | 22 | | GA | | 2-7 | 33-25-31 | | D03440 | | 4 | | S10272 | | 1 | Z2 | 115-199 | |
| 0004WO | 22 | | GA | | 3-0 | 33-25-31 | | D03440 | | 4 | | S10272 | | 1 | Z2 | 001-099 | |
| 0005RB | 22 | | GA | | 4-4 | 33-25-31 | | D03440 | | 5 | | S10271 | | 4 | BX | 115-199 | |
| 0005V | 22 | | GA | | 4-0 | 33-25-31 | | D03440 | | 5 | | S10271 | | 4 | Z1 | 001-099 | |
| 0006N | 16 | | GA | | 3-0 | 33-23-31 | | D03440 | | 6 | | SM00006 | | | WI | 001-099 | |
| 0006P | 16 | | GA | | 3-2 | 33-23-31 | | D03440 | | 6 | | SM00006 | | | WI | 115-199 | |
| 0007L | 20 | | GA | | 3-7 | 33-24-31 | | D03440 | | 7 | | L00447 | | NS | AB | 115-199 | |
| 0007W | 20 | | GA | | 4-0 | 33-24-31 | | D03440 | | 7 | | L00447 | | NS | AB | 001-099 | |
| 0008N | 16 | | GA | | 3-3 | 33-23-31 | | D03440 | | 8 | | SM00008 | | | WI | 115-199 | |
| 0008O | 16 | | GA | | 3-0 | 33-23-31 | | D03440 | | 8 | | SM00008 | | | WI | 001-099 | |
| 0009A | 22 | | GA | | 2-7 | 33-25-31 | | D03440 | | 9 | | S10272 | | 4 | Z2 | 115-199 | |
| 0010K | 18 | | GA | | 3-0 | 35-21-31 | | D03440 | | 10 | | SP03024 | | | WI | 001-099 | |
| 0010K | 18 | | GA | | 2-8 | 35-21-31 | | D03440 | | 10 | | SP01000 | | | WI | 115-199 | |
| 0011G | 20 | | GA | | 3-0 | 35-21-31 | | D03440 | | 11 | | SP03026 | | | WI | 001-099 | |
| 0011RG | 20 | | GA | | 2-8 | 35-21-31 | | D03440 | | 11 | | SP00500 | | | 9 | 115-199 | |
| 0018BO | 18 | | GA | | 4-0 | 33-24-31 | | L00447 | GND | AB | | SM00008 | | | WI | 001-099 | |
| 0018N | 16 | | GA | | 2-11 | 33-24-31 | | L00447 | GND | BY | | SM00008 | | | WI | 115-199 | |
| 0020AH | 22 | | GA | | 3-0 | 33-25-31 | | S10271 | | 1 | Z1 | SP03024 | | | WI | 001-099 | |
| 0020K | 18 | | GA | | 3-0 | 33-25-31 | | S10271 | | 1 | Z1 | SP01000 | | | WI | 115-199 | |
| 0022RY | 22 | | GA | | 2-7 | 33-25-31 | | S10272 | | 5 | Z2 | S10271 | | 3 | BX | 115-199 | |
| 0023RL | 22 | | GA | | 2-7 | 33-25-31 | | S10271 | | 2 | BX | S10272 | | 2 | Z2 | 115-199 | |
| 0023WK | 22 | | GA | | 3-0 | 33-25-31 | | S10271 | | 2 | Z1 | S10272 | | 2 | Z2 | 001-099 | |
| 0026N | 16 | | GA | | 2-0 | 33-23-31 | | SM00006 | | | WI | S10273 | | 1 | BV | 001-099 | |
| 0026P | 16 | | GA | | 1-2 | 33-23-31 | | SM00006 | | | WI | S10273 | | 1 | BV | 115-199 | |
| 0028N | 16 | | GA | | 1-2 | 33-23-31 | | SM00008 | | | WI | L00448A | = G | | L | 115-199 | |
| 0028O | 16 | | GA | | 2-0 | 33-23-31 | | SM00008 | | | WI | L00448A | = G | | L | 001-099 | |
| 0036N | 16 | | GA | | 2-0 | 33-23-31 | | S10274 | | 1 | BV | SM00006 | | | WI | 001-099 | |
| 0036P | 16 | | GA | | 1-6 | 33-23-31 | | S10274 | | 1 | BV | SM00006 | | | WI | 115-199 | |
| 0038N | 16 | | GA | | 1-6 | 33-23-31 | | SM00008 | | | WI | L00448B | = G | | L | 115-199 | |
| 0038O | 16 | | GA | | 2-0 | 33-23-31 | | SM00008 | | | WI | L00448B | = G | | L | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W0510

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|--------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0512 | 286N0512 | | | PASSENGER SERVICE UNIT-FULL (UNDER BIN) (continued) | | | | | | | | | | | |
| 0046N | 16 | | GA | | 3-0 | 33-23-31 | S10275 | 1 | BV | | SM00006 | | WI | | 001-099 |
| 0046P | 16 | | GA | | 2-2 | 33-23-31 | S10275 | 1 | BV | | SM00006 | | WI | | 115-199 |
| 0048N | 16 | | GA | | 1-11 | 33-23-31 | L00448C | =G | L | | SM00008 | | WI | | 115-199 |
| 0048O | 16 | | GA | | 3-0 | 33-23-31 | L00448C | =G | L | | SM00008 | | WI | | 001-099 |
| 0056N | 16 | | GA | | 2-0 | 33-23-31 | L00448A | =P | L | | S10273 | 2 | BV | | 001-099 |
| 0056P | 16 | | GA | | 1-7 | 33-23-31 | L00448A | =P | L | | S10273 | 2 | BV | | 115-199 |
| 0066N | 16 | | GA | | 2-0 | 33-23-31 | L00448B | =P | L | | S10274 | 2 | BV | | 001-099 |
| 0066P | 16 | | GA | | 1-6 | 33-23-31 | L00448B | =P | L | | S10274 | 2 | BV | | 115-199 |
| 0076N | 16 | | GA | | 2-0 | 33-23-31 | L00448C | =P | L | | S10275 | 2 | BV | | 001-099 |
| 0076P | 16 | | GA | | 1-5 | 33-23-31 | L00448C | =P | L | | S10275 | 2 | BV | | 115-199 |
| 2001B | 22 | | GB | A | 4-0 | 23-31-42 | D03440 | | 14 | | M10342 | COM | AC | | 001-099 |
| 2001B | 22 | | HB | A | 4-4 | 23-31-42 | D03440 | | 13 | | M10342 | COM | AC | | 115-199 |
| 2001R | 22 | | GB | A | 0-0 | 23-31-42 | D03440 | | 13 | | M10342 | 2K | AD | | 001-099 |
| 2001R | 22 | | HB | A | 0-0 | 23-31-42 | D03440 | | 14 | | M10342 | 2K | AD | | 115-199 |
| A-A | | | | | 0-0 | 35-21-31 | B10054 | | GRN | | SP03024 | | WI | | 001-099 |
| A-B | | | | | 0-0 | 35-21-31 | B10054 | | RED | | SP03026 | | WI | | 001-099 |
| D-G | | | | | 0-0 | 35-21-31 | B10054 | | GRN | | SP01000 | | WI | | 115-199 |
| D-P | | | | | 0-0 | 35-21-31 | B10054 | | RED | | SP00500 | | 9 | | 115-199 |
| W0513 | 286N0513 | | | PASSENGER ADDRESS MUTED SPKR-DR. 2 | | | | | | | | | | | |
| 0001 | 22 | | GA | | 6-0 | 23-31-21 | D01239 | | 3 | | D01235 | 3 | | | ALL |
| 0002 | 22 | | GA | | 6-0 | 23-31-21 | D01239 | | 4 | | D01235 | 7 | | | ALL |
| 2001B | 22 | | GB | AA | 6-0 | 23-31-21 | D01239 | | 1 | | D01235 | 2 | | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 23-31-21 | D01239 | | 2 | | D01235 | 6 | | | ALL |
| 2002B | 22 | | GB | AB | 6-0 | 23-31-21 | D04707P | | 1 | VG | * | D01235 | 4 | | ALL |
| 2002R | 22 | | GB | AB | 0-0 | 23-31-21 | D04705J | | 1 | VY | * | D01235 | 8 | | ALL |
| 2003B | 22 | | GB | AC | 6-0 | 23-31-21 | D04707P | | 1 | VG | * | B10116 | COM | AC | ALL |
| 2003R | 22 | | GB | AC | 0-0 | 23-31-21 | D04705J | | 1 | VY | * | B10116 | 2K | AD | ALL |
| W0514 | 286N0514 | | | PASSENGER SERVICE UNIT-FULL (UNDER BIN) | | | | | | | | | | | |
| 0001WY | 18 | | GA | | 4-0 | 33-24-31 | D03442 | | 1 | | L00449 | FSB | AB | | 001-099 |
| 0001Y | 20 | | GA | | 4-0 | 33-24-31 | D03442 | | 1 | | L00449 | FSB | AB | | 115-199 |
| 0002RY | 22 | | GA | | 3-0 | 33-25-31 | D03442 | | 2 | | S10277 | 6 | Z2 | | 115-199 |
| 0002WV | 22 | | GA | | 4-0 | 33-25-31 | D03442 | | 2 | | S10276 | 3 | Z1 | | 001-099 |
| 0003RL | 22 | | GA | | 3-0 | 33-25-31 | D03442 | | 3 | | S10277 | 3 | Z2 | | 115-199 |
| 0003WG | 22 | | GA | | 3-0 | 33-25-31 | D03442 | | 3 | | S10277 | 3 | Z2 | | 001-099 |
| 0004RN | 22 | | GA | | 4-0 | 33-25-31 | D03442 | | 4 | | S10277 | 1 | Z2 | | 115-199 |
| 0004WO | 22 | | GA | | 3-0 | 33-25-31 | D03442 | | 4 | | S10277 | 1 | Z2 | | 001-099 |
| 0005RB | 22 | | GA | | 5-0 | 33-25-31 | D03442 | | 5 | | S10276 | 4 | Z1 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0510

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0514 | 286N0514 | | | PASSENGER SERVICE UNIT-FULL (UNDER BIN) (continued) | | | | | | | | | | | |
| 0005V | 22 | GA | | | 4-0 | 33-25-31 | D03442 | | 5 | | S10276 | 4 | Z1 | | 001-099 |
| 0006N | 16 | GA | | | 3-0 | 33-23-31 | D03442 | | 6 | | SM00006 | | WI | | 001-099 |
| 0006P | 16 | GA | | | 4-0 | 33-23-31 | D03442 | | 6 | | SM00006 | | WI | | 115-199 |
| 0007L | 20 | GA | | | 4-0 | 33-24-31 | D03442 | | 7 | | L00449 | NS | AB | | 115-199 |
| 0007W | 20 | GA | | | 4-0 | 33-24-31 | D03442 | | 7 | | L00449 | NS | AB | | 001-099 |
| 0008N | 16 | GA | | | 4-0 | 33-23-31 | D03442 | | 8 | | SM00008 | | WI | | 115-199 |
| 0008O | 16 | GA | | | 3-0 | 33-23-31 | D03442 | | 8 | | SM00008 | | WI | | 001-099 |
| 0009A | 22 | GA | | | 3-0 | 33-25-31 | D03442 | | 9 | | S10277 | 4 | Z2 | | 115-199 |
| 0010K | 18 | GA | | | 3-0 | 35-21-31 | D03442 | | 10 | | SP01002 | | WI | | ALL |
| 0011G | 20 | GA | | | 3-0 | 35-21-31 | D03442 | | 11 | | SP00502 | | WI | | 001-099 |
| 0011RG | 20 | GA | | | 3-0 | 35-21-31 | D03442 | | 11 | | SP00502 | | 9 | | 115-199 |
| 0012WB | 20 | GA | | | 3-0 | 23-31-42 | D03442 | | 12 | | D00759 | 3 | | | 001-099 |
| 0015BK | 20 | GA | | | 3-0 | 23-31-42 | D03442 | | 15 | | D00759 | 3 | | | 115-199 |
| 0018BO | 18 | GA | | | 4-0 | 33-24-31 | L00449 | GND | AB | | SM00008 | | WI | | 001-099 |
| 0018N | 16 | GA | | | 3-0 | 33-24-31 | L00449 | GND | BY | | SM00008 | | WI | | 115-199 |
| 0020AH | 22 | GA | | | 3-0 | 33-25-31 | S10276 | | 1 | Z1 | SP01002 | | WI | | 001-099 |
| 0020K | 18 | GA | | | 3-0 | 33-25-31 | S10276 | | 1 | Z1 | SP01002 | | WI | | 115-199 |
| 0022RY | 22 | GA | | | 3-0 | 33-25-31 | S10277 | | 5 | Z2 | S10276 | 3 | Z1 | | 115-199 |
| 0023RL | 22 | GA | | | 2-0 | 33-25-31 | S10276 | | 2 | Z1 | S10277 | 2 | Z2 | | 115-199 |
| 0023WK | 22 | GA | | | 3-0 | 33-25-31 | S10276 | | 2 | Z1 | S10277 | 2 | Z2 | | 001-099 |
| 0026N | 16 | GA | | | 2-0 | 33-23-31 | SM00006 | | | WI | S10278 | 1 | BV | | 001-099 |
| 0026P | 16 | GA | | | 2-0 | 33-23-31 | S10278 | | 1 | BV | SM00006 | | WI | | 115-199 |
| 0028N | 16 | GA | | | 2-0 | 33-23-31 | L00450A | =G | L | | SM00008 | | WI | | 115-199 |
| 0028O | 16 | GA | | | 2-0 | 33-23-31 | SM00008 | | | WI | L00450A | =G | L | | 001-099 |
| 0030K | 20 | GA | | | 2-0 | 23-31-42 | SP01002 | | | WI | D00759 | 7 | | | 115-199 |
| 0030Y | 20 | QB | | | 2-0 | 23-31-42 | D00759 | | 7 | | SP01002 | | WI | | 001-099 |
| 0036N | 16 | GA | | | 2-0 | 33-23-31 | S10279 | | 1 | BV | SM00006 | | WI | | 001-099 |
| 0036P | 16 | GA | | | 2-0 | 33-23-31 | SM00006 | | | WI | S10279 | 1 | BV | | 115-199 |
| 0038N | 16 | GA | | | 2-0 | 33-23-31 | SM00008 | | | WI | L00450B | =G | L | | 115-199 |
| 0038O | 16 | GA | | | 2-0 | 33-23-31 | SM00008 | | | WI | L00450B | =G | L | | 001-099 |
| 0046N | 16 | GA | | | 3-0 | 33-23-31 | S10280 | | 1 | BV | SM00006 | | WI | | 001-099 |
| 0046P | 16 | GA | | | 3-0 | 33-23-31 | S10280 | | 1 | BV | SM00006 | | WI | | 115-199 |
| 0048N | 16 | GA | | | 2-0 | 33-23-31 | L00450C | =G | L | | SM00008 | | WI | | 115-199 |
| 0048O | 16 | GA | | | 3-0 | 33-23-31 | L00450C | =G | L | | SM00008 | | WI | | 001-099 |
| 0056N | 16 | GA | | | 2-0 | 33-23-31 | L00450A | =P | L | | S10278 | 2 | BV | | 001-099 |
| 0056P | 16 | GA | | | 2-0 | 33-23-31 | L00450A | =P | L | | S10278 | 2 | BV | | 115-199 |
| 0066N | 16 | GA | | | 2-0 | 33-23-31 | L00450B | =P | L | | S10279 | 2 | BV | | 001-099 |
| 0066P | 16 | GA | | | 2-0 | 33-23-31 | L00450B | =P | L | | S10279 | 2 | BV | | 115-199 |
| 0076N | 16 | GA | | | 2-0 | 33-23-31 | L00450C | =P | L | | S10280 | 2 | BV | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0510

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0514 | 286N0514 | | | PASSENGER SERVICE UNIT-FULL (UNDER BIN) (continued) | | | | | | | | | | | |
| 0076P | 16 | | GA | | 2-0 | 33-23-31 | L00450C | = P | L | | S10280 | 2 | BV | | 115-199 |
| 2001B | 22 | | GB | A | 3-0 | 23-31-42 | D03442 | | 14 | | D00759 | 2 | | | 001-099 |
| 2001B | 22 | | HB | A | 3-0 | 23-31-42 | D03442 | | 13 | | D00759 | 2 | | | 115-199 |
| 2001R | 22 | | GB | A | 0-0 | 23-31-42 | D03442 | | 13 | | D00759 | 6 | | | 001-099 |
| 2001R | 22 | | HB | A | 0-0 | 23-31-42 | D03442 | | 14 | | D00759 | 6 | | | 115-199 |
| 2002B | 22 | | GB | B | 3-0 | 23-31-42 | D00759 | | 4 | | M10343 | COM | AC | | 001-099 |
| 2002B | 22 | | HB | B | 3-0 | 23-31-42 | M10343 | COM | AC | | D00759 | 4 | | | 115-199 |
| 2002R | 22 | | GB | B | 0-0 | 23-31-42 | D00759 | | 8 | | M10343 | 2K | AD | | 001-099 |
| 2002R | 22 | | HB | B | 0-0 | 23-31-42 | M10343 | | 2K | AD | D00759 | 8 | | | 115-199 |
| A-A | | | | | 0-0 | 35-21-31 | B10055 | GRN | | | SP01002 | | WI | | 001-099 |
| A-B | | | | | 0-0 | 35-21-31 | B10055 | RED | | | SP00502 | | WI | | 001-099 |
| D-G | | | | | 0-0 | 35-21-31 | B10055 | GRN | | | SP01002 | | WI | | 115-199 |
| D-P | | | | | 0-0 | 35-21-31 | B10055 | RED | | | SP00502 | | 9 | | 115-199 |
| W0515 | 286N0515 | | | MISC MUTED SPEAKERS | | | | | | | | | | | |
| 2001B | 22 | | GB | AA | 17-0 | 23-31-31 | D04707J | | 1 | VY | B10114 | COM | AC | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 23-31-31 | D04705P | | 1 | VG | B10114 | 2K | AD | | ALL |
| W0518 | 286N0518 | | | PASSENGER SERVICE UNIT-SIGN ONLY (UNDER BIN) | | | | | | | | | | | |
| 0001 | 20 | | GA | | 4-0 | 33-24-31 | D03446 | | 1 | | L00453 | FSB | AB | | 115-199 |
| 0001WY | 18 | | GA | | 4-0 | 33-24-31 | D03446 | | 1 | | L00453 | FSB | AB | | 001-099 |
| 0007 | 20 | | GA | | 4-0 | 33-24-31 | D03446 | | 7 | | L00453 | NS | AB | | 115-199 |
| 0007W | 20 | | GA | | 4-0 | 33-24-31 | D03446 | | 7 | | L00453 | NS | AB | | 001-099 |
| 0008 | 16 | | GA | | 4-0 | 33-24-31 | D03446 | | 8 | | L00453 | GND | BY | | 115-199 |
| 0008O | 18 | | GA | | 4-0 | 33-24-31 | D03446 | | 8 | | L00453 | GND | AB | | 001-099 |
| W0519 | 286N0519 | | | MISC MUTED SPEAKERS | | | | | | | | | | | |
| 2002B | 22 | | GB | AB | 6-0 | 23-31-32 | D04701J | | 1 | VY | B10140 | COM | AC | | ALL |
| 2002R | 22 | | GB | AB | 0-0 | 23-31-32 | D04703P | | 1 | VG | B10140 | 1K | AD | | ALL |

WIRE LIST

D280N032

91-21-11
Section W0510
Page 5 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | | To | | | | | |
|---|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W0520 286N0520 ATTENDANT SERVICE UNIT (UNDER BIN) | | | | | | | | | | | | | | | | |
| 0006P | 16 | | GA | | 5-0 | 33-23-31 | D03448 | | 6 | | SM00006 | | WI | | 115-199 | |
| 0008N | 16 | | GA | | 5-0 | 33-23-31 | D03448 | | 8 | | SM00008 | | WI | | 115-199 | |
| 0010K | 18 | | GA | | 4-0 | 35-21-31 | D03448 | | 10 | | SP00518 | | 9 | | 115-199 | |
| 0011RG | 20 | | GA | | 4-0 | 35-21-31 | D03448 | | 11 | | SP00504 | | 9 | | 115-199 | |
| 0016P | 16 | | GA | | 1-0 | 33-23-31 | SM00006 | | | | S10291 | 1 | BV | | 115-199 | |
| 0026P | 16 | | GA | | 2-0 | 33-23-31 | S10331 | | 1 | BV | SM00006 | | WI | | 115-199 | |
| 0028N | 16 | | GA | | 1-0 | 33-23-31 | L00454A | =G | L | | SM00008 | | WI | | 115-199 | |
| 0038N | 16 | | GA | | 2-0 | 33-23-31 | L00454B | =G | L | | SM00008 | | WI | | 115-199 | |
| 0056P | 16 | | GA | | 1-0 | 33-23-31 | L00454A | =P | L | | S10291 | 2 | BV | | 115-199 | |
| 0066P | 16 | | GA | | 1-0 | 33-23-31 | L00454B | =P | L | | S10331 | 2 | BV | | 115-199 | |
| D-G | | | | | 0-0 | 35-21-31 | B10057 | | GRN | | SP00518 | | 9 | | 115-199 | |
| D-P | | | | | 0-0 | 35-21-31 | B10057 | | RED | | SP00504 | | 9 | | 115-199 | |
| W0522 286N0522 PASSENGER SERVICE UNIT (OVER DOOR) | | | | | | | | | | | | | | | | |
| 0002RY | 22 | | GA | | 6-8 | 33-25-31 | D03450 | | 2 | | S10287 | 6 | Z2 | | 115-199 | |
| 0002WV | 22 | | GA | | 4-11 | 33-25-31 | D03450 | | 2 | | S10286 | 3 | Z1 | | 001-099 | |
| 0003RL | 22 | | GA | | 6-8 | 33-25-31 | D03450 | | 3 | | S10287 | 3 | Z2 | | 115-199 | |
| 0003WG | 22 | | GA | | 6-1 | 33-25-31 | D03450 | | 3 | | S10287 | 3 | Z2 | | 001-099 | |
| 0004RN | 22 | | GA | | 6-8 | 33-25-31 | D03450 | | 4 | | S10287 | 1 | Z2 | | 115-199 | |
| 0004WO | 22 | | GA | | 6-1 | 33-25-31 | D03450 | | 4 | | S10287 | 1 | Z2 | | 001-099 | |
| 0005RB | 22 | | GA | | 5-4 | 33-25-31 | D03450 | | 5 | | S10286 | 4 | Z1 | | 115-199 | |
| 0005V | 22 | | GA | | 4-9 | 33-25-31 | D03450 | | 5 | | S10286 | 4 | Z1 | | 001-099 | |
| 0006N | 16 | | GA | | 4-5 | 33-23-31 | D03450 | | 6 | | SM00001 | | WI | | 001-099 | |
| 0006P | 16 | | GA | | 5-0 | 33-23-31 | D03450 | | 6 | | SM00001 | | WI | | 115-199 | |
| 0008N | 16 | | GA | | 5-2 | 33-23-31 | D03450 | | 8 | | SM00008 | | WI | | 115-199 | |
| 0008O | 16 | | GA | | 4-7 | 33-23-31 | D03450 | | 8 | | SM00008 | | WI | | 001-099 | |
| 0009A | 22 | | GA | | 6-8 | 33-25-31 | D03450 | | 9 | | S10287 | 4 | Z2 | | 115-199 | |
| 0010K | 18 | | GA | | 3-11 | 35-21-31 | D03450 | | 10 | | SP01004 | | WI | | 001-099 | |
| 0010K | 18 | | GA | | 4-7 | 35-21-31 | D03450 | | 10 | | SP01004 | | WI | | 115-199 | |
| 0011G | 20 | | GA | | 3-11 | 35-21-31 | D03450 | | 11 | | SP00506 | | 9 | | 001-099 | |
| 0011RG | 20 | | GA | | 4-7 | 35-21-31 | D03450 | | 11 | | SP00506 | | 9 | | 115-199 | |
| 0020AH | 22 | | GA | | 1-11 | 33-25-31 | S10286 | | 1 | Z1 | SP01004 | | WI | | 001-099 | |
| 0020K | 18 | | GA | | 1-10 | 33-25-31 | S10286 | | 1 | Z1 | SP01004 | | WI | | 115-199 | |
| 0022RY | 22 | | GA | | 2-10 | 33-25-31 | S10287 | | 5 | Z2 | S10286 | 3 | Z1 | | 115-199 | |
| 0023RL | 22 | | GA | | 2-8 | 33-25-31 | S10286 | | 2 | Z1 | S10287 | 2 | Z2 | | 115-199 | |
| 0023WK | 22 | | GA | | 2-7 | 33-25-31 | S10286 | | 2 | Z1 | S10287 | 2 | Z2 | | 001-099 | |
| 0026N | 16 | | GA | | 0-10 | 33-23-31 | SM00001 | | | WI | S10288 | 1 | BV | | 001-099 | |
| 0026P | 16 | | GA | | 0-11 | 33-23-31 | SM00001 | | | WI | S10288 | 1 | BV | | 115-199 | |
| 0028N | 16 | | GA | | 1-1 | 33-23-31 | L00455A | =G | L | | SM00008 | | WI | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W0520

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0522 | 286N0522 | | | PASSENGER SERVICE UNIT (OVER DOOR) (continued) | | | | | | | | | | | |
| 0028O | 16 | | GA | | 1-1 | 33-23-31 | L00455A | = G | C | | SM00008 | | WI | | 001-099 |
| 0036N | 16 | | GA | | 1-3 | 33-23-31 | S10289 | 1 | BV | | SM00001 | | WI | | 001-099 |
| 0036P | 16 | | GA | | 1-3 | 33-23-31 | S10289 | 1 | BV | | SM00001 | | WI | | 115-199 |
| 0038N | 16 | | GA | | 1-4 | 33-23-31 | L00455B | = G | L | | SM00008 | | WI | | 115-199 |
| 0038O | 16 | | GA | | 1-3 | 33-23-31 | L00455B | = G | C | | SM00008 | | WI | | 001-099 |
| 0056N | 16 | | GA | | 1-0 | 33-23-31 | L00455A | = P | C | | S10288 | 2 | BV | | 001-099 |
| 0056P | 16 | | GA | | 1-0 | 33-23-31 | L00455A | = P | L | | S10288 | 2 | BV | | 115-199 |
| 0066N | 16 | | GA | | 0-11 | 33-23-31 | L00455B | = P | C | | S10289 | 2 | BV | | 001-099 |
| 0066P | 16 | | GA | | 0-11 | 33-23-31 | L00455B | = P | L | | S10289 | 2 | BV | | 115-199 |
| A-A | | | | | 0-0 | 35-21-31 | B10056 | GRN | | | SP01004 | | WI | | 001-099 |
| A-B | | | | | 0-0 | 35-21-31 | B10056 | RED | | | SP00506 | | 9 | | 001-099 |
| D-G | | | | | 0-0 | 35-21-31 | B10056 | GRN | | | SP01004 | | WI | | 115-199 |
| D-P | | | | | 0-0 | 35-21-31 | B10056 | RED | | | SP00506 | | 9 | | 115-199 |
| W0524 | 286N0524 | | | PASSENGER SERVICE UNIT-OXYGEN ONLY (OVER DOOR) | | | | | | | | | | | |
| 0010 | 18 | | GA | | 5-0 | 35-21-31 | D03452 | | 10 | | SP00522 | | 9 | | 001-099 |
| 0011 | 20 | | GA | | 5-0 | 35-21-31 | D03452 | | 11 | | SP00524 | | 9 | | 001-099 |
| D-G | | | | | 0-0 | 35-21-31 | B10058 | GRN | | | SP00522 | | 9 | | 001-099 |
| D-P | | | | | 0-0 | 35-21-31 | B10058 | RED | | | SP00524 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11
Section W0520
Page 2 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|----------------------------------|---------|----------|---------|-------|------|------|---------|-------|------|-------------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type |
| W0530 | 286N0530 | | | AFT WINDSCREEN-LEFT | | | | | | | | | | | |
| 0001 | 22 | | GK | | 6-0 | 33-22-14 | D04628 | | | | D42052P | 1 | | | 001-099 |
| 0001 | 22 | | GK | | 7-0 | 33-22-14 | D04628 | | | | D42052P | 1 | | | 115-199 |
| 0002 | 22 | | GK | | 6-0 | 33-22-14 | D04628 | | | | D42052P | 2 | | | 001-099 |
| 0002 | 22 | | GK | | 7-0 | 33-22-14 | D04628 | | | | D42052P | 2 | | | 115-199 |
| 0003 | 20 | | GK | | 6-0 | 33-22-14 | D04628 | | | | D42052P | 3 | | | 001-099 |
| 0003 | 20 | | GK | | 7-0 | 33-22-14 | D04628 | | | | D42052P | 3 | | | 115-199 |
| 0004 | 22 | | GK | | 6-0 | 33-22-14 | D04628 | | | | D42052P | 4 | | | 001-099 |
| 0004 | 22 | | GK | | 7-0 | 33-22-14 | D04628 | | | | D42052P | 4 | | | 115-199 |
| 0005 | 22 | | GK | | 6-0 | SPARE | D04628 | | | | D42052P | 5 | | | 001-099 |
| 0005 | 22 | | GK | | 7-0 | 33-27-31 | D04628 | | | | D42052P | 5 | | | 115-199 |
| 0006 | 22 | | GK | | 7-0 | 33-27-31 | D04628 | | | | D42052P | 6 | | | 115-199 |
| 0007 | 22 | | GK | | 7-0 | 33-27-31 | D04628 | | | | D42052P | 7 | | | 115-199 |
| 0008 | 22 | | GK | | 7-0 | 33-27-31 | D04628 | | | | D42052P | 8 | | | 115-199 |
| 0009 | 20 | | GK | | 7-0 | 33-22-14 | D04628 | | | | D42052P | 9 | | | 115-199 |
| 0010 | 22 | | GK | | 7-0 | SPARE | D04628 | | | | D42052P | 10 | | | 115-199 |
| W0534 | 286N0534 | | | PASSENGER SERVICE UNIT-UNDER BIN | | | | | | | | | | | |
| 0002RY | 22 | | GA | | 3-0 | 33-25-31 | D04818 | | | | S10384 | 6 | Z2 | | 115-199 |
| 0003RL | 22 | | GA | | 3-0 | 33-25-31 | D04818 | | | | S10384 | 3 | Z2 | | 115-199 |
| 0004RN | 22 | | GA | | 3-0 | 33-25-31 | D04818 | | | | S10384 | 1 | Z2 | | 115-199 |
| 0005RB | 22 | | GA | | 5-0 | 33-25-31 | D04818 | | | | S10385 | 4 | Z1 | | 115-199 |
| 0006P | 16 | | GA | | 4-0 | 33-23-31 | D04818 | | | | SM00006 | | WI | | 115-199 |
| 0008N | 16 | | GA | | 4-0 | 33-23-31 | D04818 | | | | SM00008 | | WI | | 115-199 |
| 0009A | 22 | | GA | | 3-0 | 33-25-31 | D04818 | | | | S10384 | 4 | Z2 | | 115-199 |
| 0010K | 18 | | GA | | 3-0 | 35-21-31 | D04818 | | | | SP01600 | | WI | | 115-199 |
| 0011RG | 20 | | GA | | 3-0 | 35-21-31 | D04818 | | | | SP01602 | 9 | | | 115-199 |
| 0020K | 18 | | GA | | 4-0 | 33-25-31 | S10385 | | | Z1 | SP01600 | | WI | | 115-199 |
| 0022RY | 22 | | GA | | 3-0 | 33-25-31 | S10384 | | | Z2 | S10385 | 3 | Z1 | | 115-199 |
| 0023RL | 22 | | GA | | 3-0 | 33-25-31 | S10385 | | | Z1 | S10384 | 2 | Z2 | | 115-199 |
| 0026P | 16 | | GA | | 2-0 | 33-23-31 | SM00006 | | | | S10381 | 1 | BV | | 115-199 |
| 0028N | 16 | | GA | | 2-0 | 33-23-31 | SM00008 | | | | L00535A | = G | L | | 115-199 |
| 0036P | 16 | | GA | | 2-0 | 33-23-31 | S10382 | | | 1 | SM00006 | | WI | | 115-199 |
| 0038N | 16 | | GA | | 2-0 | 33-23-31 | SM00008 | | | | L00535B | = G | L | | 115-199 |
| 0046P | 16 | | GA | | 3-0 | 33-23-31 | S10383 | | | 1 | SM00006 | | WI | | 115-199 |
| 0048N | 16 | | GA | | 2-0 | 33-23-31 | L00535C | = G | | L | SM00008 | | WI | | 115-199 |
| 0056P | 16 | | GA | | 2-0 | 33-23-31 | L00535A | = P | | L | S10381 | 2 | BV | | 115-199 |
| 0066P | 16 | | GA | | 2-0 | 33-23-31 | L00535B | = P | | L | S10382 | 2 | BV | | 115-199 |
| 0076P | 16 | | GA | | 2-0 | 33-23-31 | L00535C | = P | | L | S10383 | 2 | BV | | 115-199 |
| 2001B | 22 | | HB | A | 5-0 | 23-31-16 | D04818 | | | | M10588 | COM | AC | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0530

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------|-------|----------|---|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0534 | 286N0534 | | | | | | PASSENGER SERVICE UNIT-UNDER BIN (continued) | | | | | | | | |
| 2001R | 22 | | HB | A | 0-0 | 23-31-16 | D04818 | | 14 | | M10588 | 2K | AD | | 115-199 |
| D-G | | | | | 0-0 | 35-21-31 | B10068 | | GRN | | SP01600 | | WI | | 115-199 |
| D-P | | | | | 0-0 | 35-21-31 | B10068 | | RED | | SP01602 | | 9 | | 115-199 |
| W0536 | 286N0536 | | | | | | PASSENGER SERVICE UNIT-(OXYGEN AND SPEAKER ONLY) | | | | | | | | |
| 0010K | 18 | | GA | | 3-0 | 35-21-31 | D03486 | | 10 | | SP03030 | | WI | | 004-099 |
| 0011G | 20 | | GA | | 3-0 | 35-21-31 | D03486 | | 11 | | SP03032 | | WI | | 004-099 |
| 2001B | 22 | | GB | A | 3-0 | 23-31-42 | D03486 | | 14 | | M10648 | COM | AC | | 004-099 |
| 2001R | 22 | | GB | A | 0-0 | 23-31-42 | D03486 | | 13 | | M10648 | 2K | AD | | 004-099 |
| A-A | | | | | 0-0 | 35-21-31 | B10071 | | GRN | | SP03030 | | WI | | 004-099 |
| A-B | | | | | 0-0 | 35-21-31 | B10071 | | RED | | SP03032 | | WI | | 004-099 |

WIRE LIST

D280N032

91-21-11

Section W0530

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | Effectivity | |
|------------------------|-------------|----|----|-----|----------------------------------|----------|--------|------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0540 | 286N0540 | | | | P76 MID/FWDATTENDANT PANEL-RIGHT | | | | | | | | | | | | |
| 0001 | 22 | | 1E | | 2-0 | 33-22-12 | D04786 | | 1 | | | S10159 | C | Z1 | | 115-199 | |
| 0002 | 22 | | 1E | | 2-0 | 33-22-12 | D04786 | | 3 | | | S10159 | - | Z1 | | 115-199 | |
| 0003 | 22 | | 1E | | 2-0 | 33-22-12 | D04786 | | 2 | | | SM00001 | | WI | | 115-199 | |
| 0004 | 22 | | 1E | | 1-0 | 33-22-12 | S10159 | | NO | Z1 | | SM00001 | | WI | | 115-199 | |
| 0005 | 22 | | 1E | | 1-0 | 33-22-12 | S10159 | | + | Z1 | | SM00001 | | WI | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W0540

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0558 | 286N0558 | | | LEFT FWD WINDSCREEN DR 1 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 6-1 | 33-22-11 | D05116 | | | | D40882P | 1 | | | 001-099 |
| 0002 | 22 | | GA | | 6-1 | 33-22-11 | D05116 | | | | D40882P | 2 | | | 001-099 |
| 0003 | 22 | | GA | | 6-1 | 33-22-11 | D05116 | | | | D40882P | 3 | | | 001-099 |
| 0004 | 20 | | GA | | 6-1 | 33-22-11 | D05116 | | | | D40882P | 4 | | | 001-099 |
| 0005 | 22 | | GA | | 6-1 | 33-22-11 | D05116 | | | | D40882P | 5 | | | 001-099 |
| 0006 | 22 | | GA | | 6-1 | 33-22-11 | D05116 | | | | D40882P | 6 | | | 001-099 |
| 0007 | 22 | | GA | | 6-1 | 33-22-11 | D05116 | | | | D40882P | 7 | | | 001-099 |
| 0008 | 22 | | GA | | 6-1 | 33-22-11 | D05116 | | | | D40882P | 8 | | | 001-099 |
| 0009 | 22 | | GA | | 6-1 | 24-51-51 | D05116 | | | | D40882P | 9 | | | 001-099 |
| 0010 | 22 | | GA | | 6-1 | 24-51-51 | D05116 | | | | D40882P | 10 | | | 001-099 |
| 0011 | 20 | | GA | | 6-1 | 24-51-51 | D05116 | | | | D40882P | 11 | | | 001-099 |
| 0012 | 20 | | GA | | 6-1 | 24-51-51 | D05116 | | | | D40882P | 12 | | | 001-099 |
| 0013 | 24 | | GK | | 6-1 | 33-21-11 | D05116 | | | | D40882P | 13 | | | 001-099 |
| 0014 | 24 | | GK | | 6-1 | 33-21-11 | D05116 | | | | D40882P | 14 | | | 001-099 |
| 0015 | 24 | | GK | | 6-1 | 33-21-11 | D05116 | | | | D40882P | 15 | | | 001-099 |
| 0016 | 22 | | GA | | 6-1 | 33-21-51 | D05116 | | | | D40882P | 16 | | | 001-099 |
| 0017 | 20 | | GA | | 6-1 | 33-21-51 | D05116 | | | | D40882P | 17 | | | 001-099 |
| 0018 | 24 | | GK | | 6-1 | 33-21-31 | D05116 | | | | D40882P | 18 | | | 001-099 |
| 0019 | 24 | | GK | | 6-1 | 33-21-31 | D05116 | | | | D40882P | 19 | | | 001-099 |
| 0020 | 24 | | GK | | 6-1 | 33-21-31 | D05116 | | | | D40882P | 20 | | | 001-099 |
| 0021 | 20 | | GA | | 6-1 | SPARE | D05116 | | | | D40882P | 21 | | | 001-099 |
| 0022 | 22 | | GA | | 6-1 | SPARE | D05116 | | | | D40882P | 22 | | | 001-099 |
| 0023 | 20 | | GA | | 6-1 | 23-34-15 | D05116 | | | | D40882P | 23 | | | 001-099 |
| 0024 | 24 | | GK | | 6-1 | 33-21-31 | D05116 | | | | D40882P | 24 | | | 001-099 |
| 0025 | 20 | | GA | | 6-1 | 23-34-15 | D05116 | | | | D40882P | 25 | | | 001-099 |
| 0029 | 22 | | GA | | 6-1 | SPARE | D05116 | | | | D40882P | 29 | | | 001-099 |
| 0030 | 22 | | GA | | 6-1 | SPARE | D05116 | | | | D40882P | 30 | | | 001-099 |
| 0031 | 20 | | GA | | 6-1 | SPARE | D05116 | | | | D40882P | 31 | | | 001-099 |
| 0032 | 22 | | GA | | 6-1 | 23-34-15 | D05116 | | | | D40882P | 32 | | | 001-099 |
| 0033 | 22 | | GA | | 6-1 | 23-34-15 | D05116 | | | | D40882P | 33 | | | 001-099 |
| 0034 | 20 | | GA | | 6-1 | 33-21-11 | D05116 | | | | D40882P | 34 | | | 001-099 |
| 0035 | 22 | | GA | | 6-1 | SPARE | D05116 | | | | D40882P | 35 | | | 001-099 |
| 0036 | 22 | | GA | | 6-1 | SPARE | D05116 | | | | D40882P | 36 | | | 001-099 |
| 0037 | 22 | | GA | | 6-1 | SPARE | D05116 | | | | D40882P | 37 | | | 001-099 |
| 0038 | 22 | | GA | | 6-1 | 33-51-11 | D05116 | | | | D40882P | 38 | | | 001-099 |
| 0039 | 22 | | GA | | 6-1 | 33-51-11 | D05116 | | | | D40882P | 39 | | | 001-099 |
| 0040 | 22 | | GA | | 6-1 | 33-51-11 | D05116 | | | | D40882P | 40 | | | 001-099 |
| 0041 | 20 | | GA | | 6-1 | 33-51-11 | D05116 | | | | D40882P | 41 | | | 001-099 |
| 3001B | 22 | | GC | AA | 6-1 | SPARE | D05116 | | | | D40882P | 28 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0550

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | |
|------------------------|-----------------|----|----|---|-------|---------|--------|------|------|--------|---------|------|------|--------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice Effectivity |
| W0558 | 286N0558 | | | LEFT FWD WINDSCREEN DR 1 (continued) | | | | | | | | | | |
| 3001R | 22 | GC | AA | | 0-0 | SPARE | D05116 | 26 | | | D40882P | 26 | | 001-099 |
| 3001Y | 22 | GC | AA | | 0-0 | SPARE | D05116 | 27 | | | D40882P | 27 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W0550

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0608 | 286N0608 | | | FOWARD GALLEY LIGHT ASSEMBLY (G1A) | | | | | | | | | | | |
| 0001 | 20 | GA | | | 1-1 | 33-27-11 | D03474 | | 1 | | D04038 | A2 | | | ALL |
| 0002 | 20 | GA | | | 1-3 | 33-27-11 | D03474 | | 2 | | SM00002 | | WI | | ALL |
| 0003 | 22 | GA | | | 1-1 | 33-27-11 | D03474 | | 3 | | SM00003 | | WI | | ALL |
| 0004 | 20 | GA | | | 1-3 | 33-27-11 | D03474 | | 4 | | SM00004 | | WI | | ALL |
| 0005 | 22 | GA | | | 1-1 | 33-27-11 | D03474 | | 5 | | D04038 | X1 | | | ALL |
| 0006 | 22 | GA | | | 1-2 | 33-27-11 | D03474 | | 6 | | D04040 | X1 | | | ALL |
| 0011 | 20 | GA | | | 1-4 | 33-27-11 | D04028 | | 1 | | SM00001 | | WI | | ALL |
| 0012 | 20 | GA | | | 1-4 | 33-27-11 | D04028 | | 2 | | SM00002 | | WI | | ALL |
| 0013 | 22 | GA | | | 2-0 | 33-27-11 | D04028 | | 3 | | D04040 | A2 | | | ALL |
| 0014 | 20 | GA | | | 1-4 | 33-27-11 | D04028 | | 4 | | SM00004 | | WI | | ALL |
| 0021 | 20 | GA | | | 2-3 | 33-27-11 | D04030 | | 1 | | D04040 | B3 | | | ALL |
| 0022 | 20 | GA | | | 1-7 | 33-27-11 | D04030 | | 2 | | SM00002 | | WI | | ALL |
| 0023 | 22 | GA | | | 1-11 | 33-27-11 | D04030 | | 3 | | SM00003 | | WI | | ALL |
| 0024 | 20 | GA | | | 1-7 | 33-27-11 | D04030 | | 4 | | SM00004 | | WI | | ALL |
| 0031 | 20 | GA | | | 1-2 | 33-27-11 | D04040 | | B2 | | SM00001 | | WI | | ALL |
| 0032 | 20 | GA | | | 1-2 | 33-27-11 | D04040 | | X2 | | SM00002 | | WI | | ALL |
| 0033 | 22 | GA | | | 1-1 | 33-27-11 | D04040 | | A3 | | SM00003 | | WI | | ALL |
| 0041 | 20 | GA | | | 1-2 | 33-27-11 | D04038 | | A3 | | SM00001 | | WI | | ALL |
| 0042 | 20 | GA | | | 1-2 | 33-27-11 | D04038 | | X2 | | SM00002 | | WI | | ALL |
| 0084 | 20 | GA | | | 1-4 | 33-27-11 | SM00004 | | WI | | GD01587 | ST.. | E | | ALL |
| A-A | | | | | 0-0 | 33-27-11 | D04028 | | 9 | | L00461 | =A | | | ALL |
| A-B | | | | | 0-0 | 33-27-11 | D04028 | | 10 | | L00461 | =B | | | ALL |
| A-C | | | | | 0-0 | 33-27-11 | D04028 | | 11 | | L00461 | =C | | | ALL |
| A-D | | | | | 0-0 | 33-27-11 | D04028 | | 12 | | L00461 | =D | | | ALL |
| B-A | | | | | 0-0 | 33-27-11 | D04028 | | 5 | | L00462 | =A | | | ALL |
| B-B | | | | | 0-0 | 33-27-11 | D04028 | | 6 | | L00462 | =B | | | ALL |
| B-C | | | | | 0-0 | 33-27-11 | D04028 | | 7 | | L00462 | =C | | | ALL |
| B-D | | | | | 0-0 | 33-27-11 | D04028 | | 8 | | L00462 | =D | | | ALL |
| C-A | | | | | 0-0 | 33-27-11 | D04030 | | 9 | | L00463 | =A | | | ALL |
| C-B | | | | | 0-0 | 33-27-11 | D04030 | | 10 | | L00463 | =B | | | ALL |
| C-C | | | | | 0-0 | 33-27-11 | D04030 | | 11 | | L00463 | =C | | | ALL |
| C-D | | | | | 0-0 | 33-27-11 | D04030 | | 12 | | L00463 | =D | | | ALL |
| D-A | | | | | 0-0 | 33-27-11 | D04030 | | 5 | | L00464 | =A | | | ALL |
| D-B | | | | | 0-0 | 33-27-11 | D04030 | | 6 | | L00464 | =B | | | ALL |
| D-C | | | | | 0-0 | 33-27-11 | D04030 | | 7 | | L00464 | =C | | | ALL |
| D-D | | | | | 0-0 | 33-27-11 | D04030 | | 8 | | L00464 | =D | | | ALL |

WIRE LIST

D280N032

91-21-11
Section W0600
Page 1 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0612 | | 286N0612 | | | | AFT GALLEY LIGHT ASSEMBLY (G4B) | | | | | | | | | |
| 0001 | 20 | GA | | | 1-3 | 33-27-31 | D03478 | 1 | | | D04044 | A2 | | | ALL |
| 0002 | 20 | GA | | | 1-3 | 33-27-31 | D03478 | 2 | | | SM00002 | | WI | | ALL |
| 0003 | 22 | GA | | | 2-2 | 33-27-31 | D03478 | 3 | | | D04036 | 3 | | | ALL |
| 0004 | 20 | GA | | | 1-3 | 33-27-31 | D03478 | 4 | | | SM00004 | | WI | | ALL |
| 0005 | 22 | GA | | | 1-3 | 33-27-31 | D03478 | 5 | | | D04044 | X1 | | | ALL |
| 0011 | 20 | GA | | | 2-4 | 33-27-31 | D04036 | 1 | | | D04044 | A3 | | | ALL |
| 0012 | 20 | GA | | | 1-6 | 33-27-31 | D04036 | 2 | | | SM00002 | | WI | | ALL |
| 0014 | 20 | GA | | | 1-6 | 33-27-31 | D04036 | 4 | | | SM00004 | | WI | | ALL |
| 0022 | 20 | GA | | | 1-5 | 33-27-31 | D04044 | X2 | | | SM00002 | | WI | | ALL |
| 0044 | 20 | GA | | | 3-5 | 33-27-31 | SM00004 | | WI | | GD01589 | ST.. | E | | ALL |
| A-A | | | | | 0-0 | 33-27-31 | D04036 | 9 | | | L00469 | =A | | | ALL |
| A-B | | | | | 0-0 | 33-27-31 | D04036 | 10 | | | L00469 | =B | | | ALL |
| A-C | | | | | 0-0 | 33-27-31 | D04036 | 11 | | | L00469 | =C | | | ALL |
| A-D | | | | | 0-0 | 33-27-31 | D04036 | 12 | | | L00469 | =D | | | ALL |
| B-A | | | | | 0-0 | 33-27-31 | D04036 | 5 | | | L00470 | =A | | | ALL |
| B-B | | | | | 0-0 | 33-27-31 | D04036 | 6 | | | L00470 | =B | | | ALL |
| B-C | | | | | 0-0 | 33-27-31 | D04036 | 7 | | | L00470 | =C | | | ALL |
| B-D | | | | | 0-0 | 33-27-31 | D04036 | 8 | | | L00470 | =D | | | ALL |
| W0614 | | 286N0614 | | | | FLUORESCENT LIGHT ASSY | | | | | | | | | |
| 0001 | 20 | GA | | | 0-11 | 33-22-11 | D03472 | 1 | | | D04014 | A2 | | | ALL |
| 0002 | 20 | GA | | | 1-4 | 33-22-11 | D03472 | 2 | | | SM00002 | | W | | ALL |
| 0003 | 22 | GA | | | 1-4 | 33-22-11 | D03472 | 3 | | | SM00003 | | W | | ALL |
| 0004 | 20 | GA | | | 1-4 | 33-22-11 | D03472 | 4 | | | SM00004 | | W | | ALL |
| 0005 | 22 | GA | | | 0-11 | 33-22-11 | D03472 | 5 | | | D04014 | X1 | | | ALL |
| 0011 | 20 | GA | | | 1-7 | 33-22-11 | D04016 | 1 | | | SM00001 | | W | | ALL |
| 0012 | 20 | GA | | | 1-7 | 33-22-11 | D04016 | 2 | | | SM00002 | | W | | ALL |
| 0013 | 22 | GA | | | 1-7 | 33-22-11 | D04016 | 3 | | | SM00003 | | W | | ALL |
| 0014 | 20 | GA | | | 1-7 | 33-22-11 | D04016 | 4 | | | SM00004 | | W | | ALL |
| 0021 | 20 | GA | | | 1-3 | 33-22-11 | D04018 | 1 | | | SM00001 | | W | | ALL |
| 0022 | 20 | GA | | | 1-3 | 33-22-11 | D04018 | 2 | | | SM00002 | | W | | ALL |
| 0023 | 22 | GA | | | 1-3 | 33-22-11 | D04018 | 3 | | | SM00003 | | W | | ALL |
| 0024 | 20 | GA | | | 1-3 | 33-22-11 | D04018 | 4 | | | SM00004 | | W | | ALL |
| 0031 | 20 | GA | | | 1-3 | 33-22-11 | D04014 | A3 | | | SM00001 | | W | | ALL |
| 0032 | 20 | GA | | | 1-3 | 33-22-11 | D04014 | X2 | | | SM00002 | | W | | ALL |
| 0084 | 20 | GA | | | 1-5 | 33-22-11 | SM00004 | | W | | GD01586 | ST.. | E | | ALL |
| A-A | | | | | 0-0 | 33-22-11 | D04016 | 9 | | | L00457 | =A | | | ALL |
| A-B | | | | | 0-0 | 33-22-11 | D04016 | 10 | | | L00457 | =B | | | ALL |
| A-C | | | | | 0-0 | 33-22-11 | D04016 | 11 | | | L00457 | =C | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0610

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0614 | 286N0614 | | | FLUORESCENT LIGHT ASSY (continued) | | | | | | | | | | | |
| A-D | | | | | 0-0 | 33-22-11 | D04016 | | | 12 | L00457 | | =D | | ALL |
| B-A | | | | | 0-0 | 33-22-11 | D04016 | | | 5 | L00458 | | =A | | ALL |
| B-B | | | | | 0-0 | 33-22-11 | D04016 | | | 6 | L00458 | | =B | | ALL |
| B-C | | | | | 0-0 | 33-22-11 | D04016 | | | 7 | L00458 | | =C | | ALL |
| B-D | | | | | 0-0 | 33-22-11 | D04016 | | | 8 | L00458 | | =D | | ALL |
| C-A | | | | | 0-0 | 33-22-11 | D04018 | | | 9 | L00459 | | =A | | ALL |
| C-B | | | | | 0-0 | 33-22-11 | D04018 | | | 10 | L00459 | | =B | | ALL |
| C-C | | | | | 0-0 | 33-22-11 | D04018 | | | 11 | L00459 | | =C | | ALL |
| C-D | | | | | 0-0 | 33-22-11 | D04018 | | | 12 | L00459 | | =D | | ALL |
| D-A | | | | | 0-0 | 33-22-11 | D04018 | | | 5 | L00460 | | =A | | ALL |
| D-B | | | | | 0-0 | 33-22-11 | D04018 | | | 6 | L00460 | | =B | | ALL |
| D-C | | | | | 0-0 | 33-22-11 | D04018 | | | 7 | L00460 | | =C | | ALL |
| D-D | | | | | 0-0 | 33-22-11 | D04018 | | | 8 | L00460 | | =D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0610

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0634 | 286N0634 | | | EMERGENCY AISLE LIGHT | | | | | | | | | | | |
| 0001 | 20 | | GA | | 4-0 | 33-51-12 | D07274 | 1 | VY | | L01065 | =P | C | | ALL |
| 0002 | 20 | | GA | | 4-0 | 33-51-12 | D07276 | 1 | VG | | L01065 | =G | C | | ALL |

WIRE LIST

D280N032

91-21-11

Section W0630

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0808 | 286N0808 | | | P65 PANEL-MISC EQUIP | | | | | | | | | | | |
| 0001 | 16 | | GA | | 4-0 | 25-51-11 | D41922P | | 9 | | K10186 | CAP | Y | | 115-199 |
| 0002 | 16 | | GA | | 4-0 | 25-51-11 | D41922P | | 10 | | K10186 | CAP | Y | | 115-199 |
| 0003 | 16 | | GA | | 4-0 | 25-51-11 | D41922P | | 11 | | K10186 | CAP | Y | | 115-199 |
| 0004 | 20 | | GA | | 4-0 | 25-51-11 | D41922P | | 4 | | K10186 | CAP | Y | | 115-199 |
| 0005 | 16 | | GA | | 4-0 | 25-51-11 | D41926P | | 4 | | K10186 | CAP | Y | | 115-199 |
| 0006 | 16 | | GA | | 4-0 | 25-51-11 | D41926P | | 6 | | K10186 | CAP | Y | | 115-199 |
| 0007 | 16 | | GA | | 4-0 | 25-51-11 | D41926P | | 8 | | K10186 | CAP | Y | | 115-199 |
| 0008 | 22 | | GA | | 3-0 | 25-51-11 | D02610 | | A3 | | K10186 | CAP | Y | | 115-199 |
| 0010 | 22 | | GA | | 4-0 | 25-51-11 | TB0188Y | A001 | BJ | | D41922P | | 3 | | 115-199 |
| 0011 | 22 | | GA | | 2-0 | 25-51-11 | TB0188Y | A001 | BJ | | D02610 | | B2 | | 115-199 |
| 0012 | 22 | | GA | | 3-0 | 25-51-11 | D41926P | | 19 | | D02614 | | B2 | | 115-199 |
| 0013 | 22 | | GA | | 2-0 | 25-51-11 | TB0188Y | A002 | BJ | | D02610 | | B1 | | 115-199 |
| 0014 | 22 | | GA | | 2-0 | 25-51-11 | TB0188Y | A002 | BJ | | D02610 | | X2 | | 115-199 |
| 0015 | 22 | | GA | | 3-0 | 25-51-11 | TB0188Y | A002 | BJ | | D41926P | | 5 | | 115-199 |
| 0016 | 22 | | GA | | 2-0 | 25-51-11 | TB0188Y | C001 | BJ | | D02610 | | A2 | | 115-199 |
| 0017 | 22 | | GA | | 3-0 | 25-51-11 | TB0188Y | C001 | BJ | | D41926P | | 3 | | 115-199 |
| 0018 | 22 | | GA | | 2-0 | 25-51-11 | TB0188Y | C001 | BJ | | D02610 | | X1 | | 115-199 |
| 0019 | 22 | | GA | | 3-0 | 25-51-11 | D02614 | | A1 | | K10186 | CAP | Y | | 115-199 |
| 0020 | 22 | | GA | | 2-0 | 25-51-11 | TB0188Y | A001 | BJ | | D02614 | | B1 | | 115-199 |
| 0021 | 22 | | GA | | 3-0 | 25-51-11 | D41926P | | 13 | | D02614 | | X2 | | 115-199 |
| 0023 | 22 | | GA | | 3-0 | 25-51-11 | TB0188Y | C002 | BJ | | D02614 | | A2 | | 115-199 |
| 0024 | 22 | | GA | | 2-0 | 25-51-11 | TB0188Y | C002 | BJ | | D02614 | | X1 | | 115-199 |
| 0025 | 22 | | GA | | 2-0 | 25-51-11 | TB0188Y | C002 | BJ | | D41926P | | 9 | | 115-199 |
| 0026 | 22 | | GA | | 4-0 | 25-51-11 | D41922P | | 2 | | D02286 | | C2 | | 115-199 |
| 0027 | 20 | | GA | | 1-11 | 33-37-11 | D41922P | | 5 | | D02286 | | X1 | | 001-099 |
| 0027 | 20 | | GA | | 4-0 | 33-37-11 | D41922P | | 5 | | D02286 | | X1 | | 115-199 |
| 0028 | 22 | | GA | | 3-0 | 25-51-11 | D41926P | | 11 | | D02286 | | C1 | | 115-199 |
| 0029 | 22 | | GA | | 1-11 | 33-37-11 | D41922P | | 6 | | D02286 | | A2 | | 001-099 |
| 0029 | 20 | | GA | | 4-0 | 33-37-11 | D41922P | | 6 | | D02286 | | A2 | | 115-199 |
| 0030 | 22 | | HA | | 1-0 | 33-37-11 | T00148 | HV1 | E | | D02286 | | A1 | | 001-099 |
| 0030 | 20 | | HA | | 3-0 | 33-37-11 | T00148 | HV2 | E | | D02286 | | A1 | | 115-199 |
| 0034 | 14 | | GA | | 2-4 | 33-37-11 | T00148 | GND | E | | D41926P | | 2 | | 001-099 |
| 0034 | 14 | | GA | | 3-0 | 33-37-11 | T00148 | GND | E | | D41926P | | 2 | | 115-199 |
| 0035 | 22 | | GA | | 2-1 | 52-34-11 | D04806 | | X1 | | D41926P | | 17 | | 001-099 |
| 0035 | 22 | | GA | | 4-0 | 52-34-11 | K00031 | | Y2 | C | D41926P | | 17 | | 115-199 |
| 0036 | 20 | | GA | | 2-1 | 52-34-11 | D04808 | | A2 | | D41922P | | 12 | | 001-099 |
| 0036 | 20 | | GA | | 3-0 | 52-34-11 | K00031 | | A2 | D | D41922P | | 12 | | 115-199 |
| 0037 | 20 | | GA | | 2-1 | 52-34-11 | D04808 | | B2 | | D41922P | | 13 | | 001-099 |
| 0037 | 20 | | GA | | 3-0 | 52-34-11 | K00031 | | B2 | D | D41922P | | 13 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0800

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W0808 | | 286N0808 | | | | P65 PANEL-MISC EQUIP (continued) | | | | | | | | | |
| 0038 | 20 | GA | | | 2-1 | 52-34-11 | D04808 | C2 | | | D41922P | 14 | | | 001-099 |
| 0038 | 20 | GA | | | 3-0 | 52-34-11 | K00031 | C2 | D | | D41922P | 14 | | | 115-199 |
| 0039 | 22 | GA | | | 2-0 | 52-34-11 | D04806 | X2 | | | D41922P | 7 | | | 001-099 |
| 0039 | 22 | GA | | | 3-0 | 52-34-11 | K00031 | Y1 | C | | D41922P | 7 | | | 115-199 |
| 0040 | 12 | HA | | | 2-3 | 33-37-11 | T00148 | LV | E | | D41926P | 1 | | | 001-099 |
| 0040 | 12 | HA | | | 3-0 | 33-37-11 | T00148 | LV | E | | D41926P | 1 | | | 115-199 |
| 0041 | 20 | GA | | | 1-11 | 52-34-11 | TB0188Y | A004 | BJ | | D41926P | 14 | | | 001-099 |
| 0041 | 20 | GA | | | 4-0 | 52-34-11 | K00031 | A3 | D | * | D41926P | 14 | | | 115-199 |
| 0042 | 20 | GA | | | 1-2 | 52-34-11 | D04808 | A3 | | | D04806 | B2 | | | 001-099 |
| 0042 | 20 | GA | | | 1-0 | 52-34-11 | K00031 | A3 | D | * | K00031 | A1 | D | | 115-199 |
| 0043 | 20 | GA | | | 1-11 | 52-34-11 | TB0188Y | C004 | BJ | | D41926P | 15 | | | 001-099 |
| 0043 | 20 | GA | | | 4-0 | 52-34-11 | K00031 | B1 | D | * | D41926P | 15 | | | 115-199 |
| 0044 | 20 | GA | | | 1-2 | 52-34-11 | D04808 | B3 | | | D04806 | A2 | | | 001-099 |
| 0044 | 20 | GA | | | 1-0 | 52-34-11 | K00031 | B3 | D | | K00031 | C1 | D | * | 115-199 |
| 0045 | 20 | GA | | | 1-10 | 52-34-11 | D04808 | B1 | | | TB0188Y | C004 | BJ | | 001-099 |
| 0045 | 20 | GA | | | 1-0 | 52-34-11 | K00031 | B1 | D | * | K00031 | C3 | D | | 115-199 |
| 0046 | 20 | GA | | | 1-11 | 52-34-11 | TB0188Y | A005 | BJ | | D41926P | 16 | | | 001-099 |
| 0046 | 20 | GA | | | 4-0 | 52-34-11 | K00031 | C1 | D | * | D41926P | 16 | | | 115-199 |
| 0047 | 22 | GA | | | 2-3 | 52-34-11 | D04808 | X1 | | | D41926P | 7 | | | 001-099 |
| 0047 | 22 | GA | | | 4-0 | 52-34-11 | K00031 | X1 | C | | D41926P | 7 | | | 115-199 |
| 0048 | 22 | GA | | | 1-10 | 52-34-11 | D04808 | X2 | | | TB0188Y | C003 | BJ | | 001-099 |
| 0048 | 22 | GA | | | 3-0 | 52-34-11 | K00031 | X2 | C | | TB0188Y | C003 | BJ | | 115-199 |
| 0049 | 22 | GA | | | 1-8 | 33-37-11 | D02286 | X2 | | | TB0188Y | C003 | BJ | | 001-099 |
| 0049 | 22 | GA | | | 2-0 | 33-37-11 | D02286 | X2 | | | TB0188Y | C003 | BJ | | 115-199 |
| 0050 | 22 | GA | | | 1-10 | 52-34-11 | D41922P | 8 | | | TB0188Y | C003 | BJ | | 001-099 |
| 0050 | 22 | GA | | | 4-0 | 52-34-11 | D41922P | 8 | | | TB0188Y | C003 | BJ | | 115-199 |
| 0051 | 20 | GA | | | 1-10 | 52-34-11 | D04808 | A1 | | | TB0188Y | A004 | BJ | | 001-099 |
| 0052 | 20 | GA | | | 1-2 | 52-34-11 | D04808 | C3 | | | D04806 | C2 | | | 001-099 |
| 0053 | 20 | GA | | | 1-9 | 52-34-11 | D04806 | B1 | | | TB0188Y | C004 | BJ | | 001-099 |
| 0054 | 20 | GA | | | 1-9 | 52-34-11 | D04806 | C1 | | | TB0188Y | A005 | BJ | | 001-099 |
| 0055 | 20 | GA | | | 1-10 | 52-34-11 | D04808 | C1 | | | TB0188Y | A005 | BJ | | 001-099 |
| 0056 | 20 | GA | | | 1-9 | 52-34-11 | D04806 | A1 | | | TB0188Y | A004 | BJ | | 001-099 |
| 0074 | 20 | GA | | | 3-0 | 25-51-11 | D02610 | B3 | | | D41926P | 18 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W0800

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|----------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|-----|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0814 | 286N0814 | | | | P65 PANEL-MISC EQUIP | | | | | | | | | | | | |
| 0012 | 22 | | GA | | 4-0 | 34-22-18 | D65001P | 39 | | | | D03003 | X2 | | | 002 | |
| 0013 | 22 | | GA | | 4-0 | 34-22-18 | D65001P | 46 | | | | D03003 | X1 | | | 002 | |
| 0029 | 22 | | CQ | | 4-0 | 34-22-28 | D65003P | 39 | | | | D03005 | X2 | | | 002 | |
| 0030 | 22 | | CQ | | 4-0 | 34-22-28 | D65003P | 46 | | | | D03005 | X1 | | | 002 | |
| 0106 | 22 | | GA | | 4-0 | 34-46-14 | D03521 | 6 | | | | D65001P | 1 | | | 002 | |
| 0110 | 22 | | GA | | 4-0 | 34-46-14 | D03521 | 10 | | | | D65001P | 4 | | | 002 | |
| 0111 | 22 | | GA | | 3-0 | 34-46-14 | D03521 | 11 | | | | TB0187Z | A009 | BJ | | 002 | |
| 0112 | 22 | | GA | | 3-0 | 34-46-14 | D03521 | 12 | | | | TB0187Z | A009 | BJ | | 002 | |
| 0195 | 22 | | GA | | 5-0 | 34-46-14 | TB0187Z | A009 | BJ | | | D65001P | 5 | | | 002 | |
| 0206 | 22 | | GA | | 4-0 | 34-46-14 | D03525 | 6 | | | | D65003P | 1 | | | 002 | |
| 0210 | 22 | | GA | | 4-0 | 34-46-14 | D03525 | 10 | | | | D65003P | 2 | | | 002 | |
| 0211 | 22 | | GA | | 3-0 | 34-46-14 | D03525 | 11 | | | | TB0187Z | A009 | BJ | | 002 | |
| 0212 | 22 | | GA | | 3-0 | 34-46-14 | D03525 | 12 | | | | TB0187Z | A009 | BJ | | 002 | |
| 2501B | 22 | | GU | A | 4-0 | 34-22-28 | D65003P | 37 | | | | D03005 | D3 | | | 002 | |
| 2501R | 22 | | GU | A | 0-0 | 34-22-28 | D65003P | 36 | | | | D03005 | C3 | | | 002 | |
| 2501Z | | | | A | 0-0 | 34-22-28 | D65003P | 38 | | | | GB00187 | ST.. | 1A | | 002 | |
| 2502B | 22 | | GU | B | 4-0 | 34-22-28 | D65003P | 44 | | | | D03005 | D1 | | | 002 | |
| 2502R | 22 | | GU | B | 0-0 | 34-22-28 | D65003P | 43 | | | | D03005 | C1 | | | 002 | |
| 2502Z | | | | B | 0-0 | 34-22-28 | D65003P | 45 | | | | GB00187 | ST.. | 1A | | 002 | |
| 2503B | 22 | | GU | C | 4-0 | 34-22-18 | D65001P | 37 | | | | D03003 | D3 | | | 002 | |
| 2503R | 22 | | GU | C | 0-0 | 34-22-18 | D65001P | 36 | | | | D03003 | C3 | | | 002 | |
| 2503Z | | | | C | 0-0 | 34-22-18 | D65001P | 38 | | | | GB00187 | ST.. | 1A | | 002 | |
| 2504B | 22 | | GU | D | 4-0 | 34-22-18 | D65001P | 44 | | | | D03003 | D1 | | | 002 | |
| 2504R | 22 | | GU | D | 0-0 | 34-22-18 | D65001P | 43 | | | | D03003 | C1 | | | 002 | |
| 2504Z | | | | D | 0-0 | 34-22-18 | D65001P | 45 | | | | GB00187 | ST.. | 1A | | 002 | |
| 2505B | 22 | | GU | E | 2-0 | 34-22-28 | D03005 | D2 | | | | TB0187Y | B003 | BJ | | 002 | |
| 2505R | 22 | | GU | E | 0-0 | 34-22-28 | D03005 | C2 | | | | TB0187Y | A003 | BJ | | 002 | |
| 2505Z | | | | E | 0-0 | 34-22-28 | D03005 | DED | | | | GB00187 | ST.. | 1A | | 002 | |
| 2506B | 22 | | GU | F | 2-0 | 34-22-18 | D03003 | D2 | | | | TB0187Y | B001 | BJ | | 002 | |
| 2506R | 22 | | GU | F | 0-0 | 34-22-18 | D03003 | C2 | | | | TB0187Y | A001 | BJ | | 002 | |
| 2506Z | | | | F | 0-0 | 34-22-18 | D03003 | DED | | | | GB00187 | ST.. | 1A | | 002 | |
| 2507B | 24 | | 7K | G | 4-0 | 34-46-14 | D03521 | 4 | | | | D65001P | 3 | | | 002 | |
| 2507W | 24 | | 7K | G | 0-0 | 34-46-14 | D03521 | 2 | | | | D65001P | 2 | | | 002 | |
| 2507Z | | | | G | 0-0 | 34-46-14 | D03521 | DED | | | | D65001P | 9 | | | 002 | |
| 2508B | 24 | | 7K | H | 3-2 | 34-46-14 | D03525 | 4 | | | | D65003P | 4 | | | 002 | |
| 2508W | 24 | | 7K | H | 0-0 | 34-46-14 | D03525 | 2 | | | | D65003P | 3 | | | 002 | |
| 2508Z | | | | H | 0-0 | 34-46-14 | D03525 | DED | | | | D65003P | 5 | | | 002 | |
| 2509B | 24 | | 7K | I | 4-0 | 34-43-15 | D03521 | 3 | | | | D65001P | 11 | | | 002 | |
| 2509W | 24 | | 7K | I | 0-0 | 34-43-15 | D03521 | 13 | | | | D65001P | 10 | | | 002 | |

WIRE LIST

D280N032

91-21-11

Section W0810

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | Effectivity | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|-------------|------|--------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W0814 | 286N0814 | | | P65 PANEL-MISC EQUIP (continued) | | | | | | | | | | | |
| 2509Z | | | | I | 0-0 | 34-43-15 | D03521 | DED | | | D65001P | 12 | | 002 | |
| 2510B | 24 | 7K | J | | 4-0 | 34-43-15 | D03525 | 3 | | | D65003P | 33 | | 002 | |
| 2510W | 24 | 7K | J | | 0-0 | 34-43-15 | D03525 | 13 | | | D65003P | 34 | | 002 | |
| 2510Z | | | | J | 0-0 | 34-43-15 | D03525 | DED | | | D65003P | 35 | | 002 | |
| 2511B | 24 | 7K | K | | 3-0 | 34-43-15 | D03521 | 5 | | | TB0187Y | B005 | BJ | 002 | |
| 2511W | 24 | 7K | K | | 0-0 | 34-43-15 | D03521 | 1 | | | TB0187Y | A005 | BJ | 002 | |
| 2511Z | | | | K | 0-0 | 34-43-15 | D03521 | DED | | | GB00187 | ST.. | 1A | 002 | |
| 2512B | 24 | 7K | L | | 3-0 | 34-43-15 | D03525 | 5 | | | TB0187Y | B007 | BJ | 002 | |
| 2512W | 24 | 7K | L | | 0-0 | 34-43-15 | D03525 | 1 | | | TB0187Y | A007 | BJ | 002 | |
| 2512Z | | | | L | 0-0 | 34-43-15 | D03525 | DED | | | GB00187 | ST.. | 1A | 002 | |
| 2513B | 24 | 7K | M | | 5-0 | 34-43-15 | D65001P | 21 | | | TB0187Y | B005 | BJ | 002 | |
| 2513W | 24 | 7K | M | | 0-0 | 34-43-15 | D65001P | 20 | | | TB0187Y | A005 | BJ | 002 | |
| 2513Z | | | | M | 0-0 | 34-43-15 | D65001P | 19 | | | GB00187 | ST.. | 1A | 002 | |
| 2514B | 24 | 7K | N | | 5-0 | 34-43-15 | D65003P | 8 | | | TB0187Y | B007 | BJ | 002 | |
| 2514W | 24 | 7K | N | | 0-0 | 34-43-15 | D65003P | 7 | | | TB0187Y | A007 | BJ | 002 | |
| 2514Z | | | | N | 0-0 | 34-43-15 | D65003P | 6 | | | GB00187 | ST.. | 1A | 002 | |
| 2515B | 24 | 7K | O | | 5-0 | 34-43-15 | D65001P | 24 | | | TB0187Y | B005 | 1A | 002 | |
| 2515W | 24 | 7K | O | | 0-0 | 34-43-15 | D65001P | 23 | | | TB0187Y | A005 | BJ | 002 | |
| 2515Z | | | | O | 0-0 | 34-43-15 | D65001P | 22 | | | GB00187 | ST.. | 1A | 002 | |
| 2516B | 24 | 7K | P | | 5-0 | 34-43-15 | D65003P | 11 | | | TB0187Y | B007 | BJ | 002 | |
| 2516W | 24 | 7K | P | | 0-0 | 34-43-15 | D65003P | 10 | | | TB0187Y | A007 | BJ | 002 | |
| 2516Z | | | | P | 0-0 | 34-43-15 | D65003P | 9 | | | GB00187 | ST.. | 1A | 002 | |
| 2527B | 22 | GU | AA | | 5-0 | 34-46-14 | TB0187Y | B001 | BJ | | D65001P | 26 | | 002 | |
| 2527R | 22 | GU | AA | | 0-0 | 34-46-14 | TB0187Y | A001 | BJ | | D65001P | 25 | | 002 | |
| 2527Z | | | | AA | 0-0 | 34-46-14 | GB00187 | ST.. | 1A | | D65001P | 27 | | 002 | |
| 2528B | 22 | GU | AB | | 5-0 | 34-43-11 | TB0187Y | B003 | BJ | | D65003P | 32 | | 002 | |
| 2528R | 22 | GU | AB | | 0-0 | 34-43-11 | TB0187Y | A003 | BJ | | D65003P | 31 | | 002 | |
| 2528Z | | | | AB | 0-0 | 34-43-11 | GB00187 | ST.. | 1A | | D65003P | 30 | | 002 | |
| 2529B | 22 | GU | AC | | 5-0 | 34-43-11 | TB0187Y | B001 | BJ | | D65001P | 30 | | 002 | |
| 2529R | 22 | GU | AC | | 0-0 | 34-43-11 | TB0187Y | A001 | BJ | | D65001P | 29 | | 002 | |
| 2529Z | | | | AC | 0-0 | 34-43-11 | GB00187 | ST.. | 1A | | D65001P | 28 | | 002 | |
| 2532B | 22 | GU | AF | | 5-0 | 34-46-14 | TB0187Y | B003 | BJ | | D65003P | 26 | | 002 | |
| 2532R | 22 | GU | AF | | 0-0 | 34-46-14 | TB0187Y | A003 | BJ | | D65003P | 25 | | 002 | |
| 2532Z | | | | AF | 0-0 | 34-46-14 | GB00187 | ST.. | 1A | | D65003P | 24 | | 002 | |
| W0816 | 286N0816 | | | PANEL-P43 EXTERIOR CONTROL, FORWARD CARGO DOOR | | | | | | | | | | | |
| 0001 | 22 | GA | | | 5-0 | 52-34-11 | S10183 | 2 | C | * | SP00178 | | 9 | ALL | |
| 0002 | 22 | GA | | | 1-0 | 52-34-11 | S10183 | 2 | C | * | S10183 | 5 | C | ALL | |
| 0003 | 22 | GA | | | 5-0 | 52-34-11 | S10183 | 6 | C | | SP00182 | | 9 | ALL | |

WIRE LIST

D280N032

91-21-11

Section W0810

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|------|---------|--------|---|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W0816 | 286N0816 | | | | PANEL-P43 EXTERIOR CONTROL,FORWARD CARGO DOOR (continued) | | | | | | | | | | | | |
| 0004 | 22 | | GA | | 5-0 | 52-34-11 | | S10183 | | 1 | C | | SP00180 | | 9 | | ALL |
| 0007 | 22 | | GA | | 5-0 | 33-37-11 | | S10128 | | 2 | C | | SP00380 | | 9 | | 001-099 |
| 0007 | 18 | | GA | | 5-0 | 33-37-11 | | S10128 | | 2 | C | | SP00380 | | 9 | | 115-199 |
| 0008 | 22 | | GA | | 5-0 | 33-37-11 | | S10128 | | 3 | C | | SP00382 | | 9 | | 001-099 |
| 0008 | 18 | | GA | | 5-0 | 33-37-11 | | S10128 | | 3 | C | | SP00382 | | 9 | | 115-199 |
| W0818 | 286N0818 | | | | FWD.CARGO DOOR LIGHTS. | | | | | | | | | | | | |
| 0001 | 16 | | GA | | 7-0 | 33-37-11 | | D41136J | | 1 | | | GD00213 | AC.. | E | | ALL |
| 0002 | 16 | | GA | | 3-0 | 33-37-11 | | D41136J | | 2 | | | GD00212 | AC.. | E | | ALL |
| 0003 | 16 | | GA | | 5-0 | 33-37-11 | | D41136J | | 3 | | | SP00264 | | 9 | | ALL |
| 0004 | 16 | | GA | | 8-6 | 33-37-11 | | SP00264 | | | 9 | | SP00260 | | 9 | | ALL |
| 0005 | 16 | | GA | | 6-6 | 33-37-11 | | SP00264 | | | 9 | | SP00258 | | 9 | | ALL |
| 0006 | 16 | | GA | | 4-0 | 33-37-11 | | SP00258 | | | 9 | | SP00254 | | 9 | | ALL |
| 0007 | 16 | | GA | | 5-0 | 33-37-11 | | SP00254 | | | 9 | | SP00252 | | 9 | | ALL |
| 0008 | 16 | | GA | | 5-6 | 33-37-11 | | SP00342 | | | 9 | | GD00213 | AC.. | E | | ALL |
| 0009 | 22 | | GA | | 3-0 | 52-34-11 | | D41136J | | 6 | | | SP01712 | | 9 | | ALL |
| 0010 | 16 | | GA | | 2-0 | 33-37-11 | | SP00256 | | | 9 | | GD00213 | AC.. | E | | ALL |
| 0011 | 22 | | GA | | 3-0 | 52-34-11 | | D41136J | | 7 | | | SP01714 | | 9 | | ALL |
| 0012 | 16 | | GA | | 3-0 | 33-37-11 | | SP00344 | | | 9 | | GD00213 | AC.. | E | | ALL |
| 0013 | 16 | | GA | | 6-6 | 33-37-11 | | SP00346 | | | 9 | | GD00212 | AC.. | E | | ALL |
| 0015 | 16 | | GA | | 4-6 | 33-37-11 | | SP00262 | | | 9 | | GD00212 | AC.. | E | | ALL |
| A-A | | | | | 0-0 | 33-37-11 | | L00385 | WHT | | | | SP00252 | | 9 | | ALL |
| A-B | | | | | 0-0 | 33-37-11 | | L00386 | WHT | | | | SP00254 | | 9 | | ALL |
| A-C | | | | | 0-0 | 33-37-11 | | L00387 | WHT | | | | SP00258 | | 9 | | ALL |
| A-D | | | | | 0-0 | 33-37-11 | | L00388 | WHT | | | | SP00260 | | 9 | | ALL |
| A-E | | | | | 0-0 | 33-37-11 | | L00389 | WHT | | | | SP00264 | | 9 | | ALL |
| B-A | | | | | 0-0 | 33-37-11 | | L00385 | BLK | | | | SP00342 | | 9 | | ALL |
| B-B | | | | | 0-0 | 33-37-11 | | L00386 | BLK | | | | SP00256 | | 9 | | ALL |
| B-C | | | | | 0-0 | 33-37-11 | | L00387 | BLK | | | | SP00344 | | 9 | | ALL |
| B-D | | | | | 0-0 | 33-37-11 | | L00388 | BLK | | | | SP00346 | | 9 | | ALL |
| B-E | | | | | 0-0 | 33-37-11 | | L00389 | BLK | | | | SP00262 | | 9 | | ALL |
| C-1 | | | | | 0-0 | 52-34-11 | | S10561 | | 1 | | | SP01712 | | 9 | | ALL |
| C-2 | | | | | 0-0 | 52-34-11 | | S10561 | | 2 | | | SP01712 | CAP | Y | | ALL |
| C-3 | | | | | 0-0 | 52-34-11 | | S10561 | | 3 | | | SP01714 | | 9 | | ALL |
| C-4 | | | | | 0-0 | 52-34-11 | | S10561 | | 4 | | | SP01712 | CAP | Y | | ALL |
| C-5 | | | | | 0-0 | 52-34-11 | | S10561 | | 5 | | | SP01712 | CAP | Y | | ALL |
| C-6 | | | | | 0-0 | 52-34-11 | | S10561 | | 6 | | | SP01712 | CAP | Y | | ALL |

WIRE LIST

D280N032

91-21-11
Section W0810
Page 3 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1001 | 286N1001 | | | E6-1 SHELF BUNDLE - L | | | | | | | | | | | |
| 0022 | 18 | | GA | | 2-2 | 34-57-11 | D42163J | 21 | 18 | | GD03011 | ST.. | 2 | | 001-099 |
| 0040 | 22 | | GA | | 2-3 | 34-57-11 | D00245B | B15 | | | D45003J | 1 | | | 001-099 |
| 0041 | 22 | | GA | | 2-2 | 34-57-11 | D42005J | 7 | | | D00245C | 2 | | | 001-099 |
| 0042 | 20 | | GA | | 2-5 | 34-57-11 | D00245C | 4 | | | GD03009 | AC.. | 2 | | 001-099 |
| 0043 | 20 | | GA | | 2-5 | 34-57-11 | D00245C | 3 | | | GD03011 | ST.. | 2 | | 001-099 |
| 0044 | 20 | | GA | | 1-6 | 23-51-13 | D45003J | | | AF | GD03011 | ST.. | 2 | | 001-099 |
| 0045 | 20 | | GA | | 1-6 | 34-57-11 | D42163J | | | AG | GD03011 | ST.. | 2 | | 001-099 |
| 0046 | 20 | | GA | | 1-6 | 34-57-11 | D42163J | | | AH | GD03011 | ST.. | 2 | | 001-099 |
| 0047 | 20 | | GA | | 1-6 | 34-57-11 | D42163J | | | AI | GD03011 | ST.. | 2 | | 001-099 |
| 0048 | 20 | | GA | | 1-6 | 34-57-11 | D42005J | | | AJ | GD03011 | ST.. | 2 | | 001-099 |
| 0049 | 20 | | GA | | 1-6 | 34-22-81 | D45003J | | | AK | GD03011 | ST.. | 2 | | 001-099 |
| 0050 | 22 | | GA | | 2-5 | 34-57-11 | D00245B | C13 | | | GD03013 | DC.. | 2 | | 001-099 |
| 0051 | 22 | | GA | | 2-2 | 34-57-11 | D42163J | 12 | | | D00245B | C12 | | | 001-099 |
| 0052 | 24 | | GK | | 1-4 | 34-57-11 | D00245B | C05 | | | SM00003 | | WI | | 001-099 |
| 0053 | 24 | | GK | | 1-4 | 34-57-11 | D00245B | C08 | | | SM00003 | | WI | | 001, 009 |
| 0053 | 24 | | GK | | 1-4 | 34-57-11 | D00245B | C07 | | | SM00003 | | WI | | 002-008, 010-099 |
| 0054 | 24 | | GK | | 1-4 | 34-57-11 | D00245B | C09 | | | SM00003 | | WI | | 001-099 |
| 2005B | 22 | | GB | AV | 2-2 | 34-57-11 | D42163J | 11 | | | D00245B | C11 | | | 001-099 |
| 2005R | 22 | | GB | AV | 0-0 | 34-57-11 | D42163J | 10 | | | D00245B | C10 | | | 001-099 |
| 2504B | 24 | | G2 | AP | 2-3 | 23-51-13 | D45003J | 3 | | | D00245B | B02 | | | 001-099 |
| 2504R | 24 | | G2 | AP | 0-0 | 23-51-13 | D45003J | 4 | | | D00245B | B01 | | | 001-099 |
| 2504Z | | | | AP | 0-0 | 23-51-13 | D45003J | | | AF | D00245B | DED | | | 001-099 |
| 2505B | 24 | | 7P | AQ | 2-2 | 34-57-11 | D42163J | 1 | | | D00245B | D01 | | | 001-099 |
| 2505N | 24 | | 7P | AQ | 0-0 | 34-57-11 | D42163J | 2 | | | D00245B | D02 | | | 001-099 |
| 2505Z | | | | AQ | 0-0 | 34-57-11 | D42163J | | | AG | D00245B | DED | | | 001-099 |
| 2506B | 24 | | 7P | AR | 2-2 | 34-57-11 | D42163J | 4 | | | D00245B | D07 | | | 001-099 |
| 2506N | 24 | | 7P | AR | 0-0 | 34-57-11 | D42163J | 5 | | | D00245B | D08 | | | 001-099 |
| 2506Z | | | | AR | 0-0 | 34-57-11 | D42163J | | | AH | D00245B | DED | | | 001-099 |
| 2507B | 24 | | 7P | AS | 2-2 | 34-57-11 | D42163J | 7 | | | D00245B | D14 | | | 001-099 |
| 2507N | 24 | | 7P | AS | 0-0 | 34-57-11 | D42163J | 8 | | | D00245B | D15 | | | 001-099 |
| 2507Z | | | | AS | 0-0 | 34-57-11 | D42163J | | | AI | D00245B | DED | | | 001-099 |
| 5005B | 24 | | G2 | AT | 2-2 | 34-57-11 | D42005J | 2 | | | D00245B | B08 | | | 001-099 |
| 5005R | 24 | | G2 | AT | 0-0 | 34-57-11 | D42005J | 1 | | | D00245B | B07 | | | 001-099 |
| 5005Z | | | | AT | 0-0 | 34-57-11 | D42005J | | | AJ | D00245B | DED | | | 001-099 |
| 5006B | 24 | | G2 | AU | 2-3 | 34-22-81 | D45003J | 12 | | | D00245B | B11 | | | 001-099 |
| 5006R | 24 | | G2 | AU | 0-0 | 34-22-81 | D45003J | 13 | | | D00245B | B10 | | | 001-099 |
| 5006Z | | | | AU | 0-0 | 34-22-81 | D45003J | | | AK | D00245B | DED | | | 001-099 |
| FRAF | | | | | 0-0 | 23-51-13 | D45003J | | | AF | D45003J | 5 | | | 001-099 |
| FRAG | | | | | 0-0 | 34-57-11 | D42163J | | | AG | D42163J | 3 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1000

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|---------|------|-------------|------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W1001 | 286N1001 | | | | E6-1 SHELF BUNDLE - L (continued) | | | | | | | | | | |
| FRAH | | | | | 0-0 | 34-57-11 | D42163J | | | AH | D42163J | 6 | | | 001-099 |
| FRAI | | | | | 0-0 | 34-57-11 | D42163J | | | AI | D42163J | 9 | | | 001-099 |
| FRAJ | | | | | 0-0 | 34-57-11 | D42005J | | | AJ | D42005J | 3 | | | 001-099 |
| FRAK | | | | | 0-0 | 34-22-81 | D45003J | | | AK | D45003J | 14 | | | 001-099 |
| W1002 | 286N1002 | | | | E6 INTEGRATION - APU BATTERY OUTPUT | | | | | | | | | | |
| 0001 | *1 | | CQ | | 1-9 | 24-31-41 | D01896 | | + | Q | TB5047 | 2 | H | | 001-002 |
| 0001 | *1 | | CQ | | 4-11 | 24-31-41 | D01896 | | + | Q | TB5047 | 3 | H | | 003-099 |
| 0001 | *1 | | ZC | | 1-3 | 24-31-41 | D01896 | | + | R | TB5047 | 2 | R | | 115-199 |
| 0002 | *1 | | CQ | | 1-10 | 24-33-12 | D01896 | | - | Q | GD05108 | DC.. | IT | | 001-002 |
| 0002 | *1 | | CQ | | 4-7 | 24-33-12 | D01896 | | - | Q | GD05108 | DC.. | IT | | 003-099 |
| 0002 | *1 | | CQ | | 4-8 | 24-31-41 | D01896 | | - | Q | GD05120 | DC.. | H | | 115-199 |
| 0003 | 08 | | HA | | 3-4 | 24-31-41 | M00207 | | - | G | M10251 | =A | F | | 001-002 |
| 0003 | 08 | | HA | | 3-5 | 24-31-41 | M00207 | | - | G | M10251 | =A | F | | 003-099 |
| 0003 | 08 | | HA | | 2-9 | 24-31-41 | M00207 | | - | G | M10251 | =A | F | | 115-199 |
| 0004 | 08 | | HA | | 2-2 | 24-31-41 | M10251 | | =B | F | GD01977 | DC.. | E | | 001-002 |
| 0004 | 08 | | HA | | 2-6 | 24-31-41 | M10251 | | =B | F | GD01977 | DC.. | E | | 003-099 |
| 0004 | 08 | | HA | | 4-2 | 24-31-41 | M10251 | | =B | F | GD02308 | DC.. | E | | 115-199 |
| 0005 | *1 | | CQ | | 1-0 | 24-33-12 | TB5047 | | 3 | H8 | M10496 | A1 | F | | 001-002 |
| 0005 | *1 | | CQ | | 1-4 | 24-33-12 | TB5047 | | 2 | H8 | M10496 | A1 | F | | 003-009 |
| 0005 | *1 | | CQ | | 1-4 | 24-33-12 | TB5047 | | 2 | H | M10496 | A1 | CK | | 010-099 |
| 0012 | *1 | | CQ | | 3-8 | 24-32-41 | TB5048 | | 1 | H | T00189 | + | H | | 001-002 |
| 0012 | *1 | | CQ | | 4-0 | 24-32-41 | TB5048 | | 1 | H | T00189 | + | H | | 003-099 |
| 0012 | *1 | | CQ | | 2-7 | 49-41-11 | TB5048 | | 1 | H | T00189 | + | H | | 115-199 |
| 0014 | *1 | | CQ | | 1-9 | 24-32-41 | T00189 | | - | R | GD05102 | DC.. | IT | | 001-002 |
| 0014 | *1 | | CQ | | 3-5 | 24-32-41 | T00189 | | - | R | GD05102 | DC.. | IT | | 003-099 |
| 0014 | *1 | | ZC | | 1-3 | 49-41-11 | T00189 | | - | R | GD05124 | DC.. | IT | | 115-199 |
| W1003 | 286N1003 | | | | E6-1 SHELF | | | | | | | | | | |
| 0004 | 20 | | GA | | 1-6 | 34-22-91 | D45007J | | | AO | GD01964 | ST.. | 2 | | 001-099 |
| 0022 | 18 | | GA | | 2-2 | 34-57-21 | D41993J | | 21 | 18 | GD01964 | ST.. | 2 | | 001-099 |
| 0162 | 20 | | GA | | 2-3 | 34-57-21 | D00443C | | 4 | | GD01963 | AC.. | 2 | | 001-099 |
| 0163 | 20 | | GA | | 2-4 | 34-57-21 | D00443C | | 3 | | GD01964 | ST.. | 2 | | 001-099 |
| 0164 | 22 | | GA | | 2-2 | 34-57-21 | D00443B | | C12 | | D41993J | 12 | | | 001-099 |
| 0165 | 24 | | GK | | 2-2 | 34-57-21 | D00443B | | B15 | | D45007J | 1 | | | 001-099 |
| 0166 | 22 | | GA | | 2-4 | 34-57-21 | D00443B | | C13 | | GD01964 | DC.. | 2 | | 001-099 |
| 0167 | 20 | | GA | | 1-6 | 34-57-21 | D41681J | | | BS | GD01964 | ST.. | 2 | | 001-099 |
| 0168 | 20 | | GA | | 1-6 | 34-57-21 | D41993J | | | BL | GD01964 | ST.. | 2 | | 001-099 |
| 0169 | 20 | | GA | | 1-6 | 34-57-21 | D41993J | | | BM | GD01964 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1000

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1003 | 286N1003 | | | E6-1 SHELF (continued) | | | | | | | | | | | |
| 0170 | 20 | | GA | | 1-6 | 34-57-21 | D41993J | | | | BN | GD01964 | ST.. | 2 | 001-099 |
| 0172 | 24 | | GK | | 0-9 | 34-57-21 | D00443B | | C09 | | | SM00001 | | WI | 001-099 |
| 0173 | 24 | | GK | | 0-9 | 34-57-21 | D00443B | | C08 | | | SM00001 | | WI | 001, 009 |
| 0173 | 24 | | GK | | 0-9 | 34-57-21 | D00443B | | C07 | | | SM00001 | | WI | 002-008, 010-099 |
| 0174 | 24 | | GK | | 0-9 | 34-57-21 | D00443B | | C05 | | | SM00001 | | WI | 001-099 |
| 1001 | 22 | | GT | B0 | 2-1 | 34-57-21 | D41681J | | 7 | | | D00443C | | 2 | 001-099 |
| 1001Z | | | | B0 | 0-0 | 34-57-21 | D41681J | | DED | | | D00443C | DED | | 001-099 |
| 2028B | 22 | | GB | BR | 2-2 | 34-57-21 | D00443B | | C11 | | | D41993J | | 11 | 001-099 |
| 2028R | 22 | | GB | BR | 0-0 | 34-57-21 | D00443B | | C10 | | | D41993J | | 10 | 001-099 |
| 2510B | 24 | | 7P | BL | 2-2 | 34-57-21 | D00443B | | D01 | | | D41993J | | 1 | 001-099 |
| 2510N | 24 | | 7P | BL | 0-0 | 34-57-21 | D00443B | | D02 | | | D41993J | | 2 | 001-099 |
| 2510Z | | | | BL | 0-0 | 34-57-21 | D00443B | | DED | | | D41993J | | | BL 001-099 |
| 2511B | 24 | | 7P | BM | 2-2 | 34-57-21 | D00443B | | D07 | | | D41993J | | 4 | 001-099 |
| 2511N | 24 | | 7P | BM | 0-0 | 34-57-21 | D00443B | | D08 | | | D41993J | | 5 | 001-099 |
| 2511Z | | | | BM | 0-0 | 34-57-21 | D00443B | | DED | | | D41993J | | | BM 001-099 |
| 2512B | 24 | | 7P | BN | 2-2 | 34-57-21 | D00443B | | D14 | | | D41993J | | 7 | 001-099 |
| 2512N | 24 | | 7P | BN | 0-0 | 34-57-21 | D00443B | | D15 | | | D41993J | | 8 | 001-099 |
| 2512Z | | | | BN | 0-0 | 34-57-21 | D00443B | | DED | | | D41993J | | | BN 001-099 |
| 2513B | 24 | | G2 | BP | 2-2 | 23-51-13 | D00443B | | B02 | | | D45007J | | 3 | 001-099 |
| 2513R | 24 | | G2 | BP | 0-0 | 23-51-13 | D00443B | | B01 | | | D45007J | | 4 | 001-099 |
| 2513Z | | | | BP | 0-0 | 23-51-13 | D00443B | | DED | | | D45007J | | 5 | 001-099 |
| 5001B | 24 | | G2 | AO | 2-2 | 34-22-91 | D45007J | | 12 | | | D00443B | B11 | | 001-099 |
| 5001R | 24 | | G2 | AO | 0-0 | 34-22-91 | D45007J | | 13 | | | D00443B | B10 | | 001-099 |
| 5001Z | | | | AO | 0-0 | 34-22-91 | D45007J | | | | AO | D00443B | DED | | 001-099 |
| 5017B | 24 | | G2 | BS | 2-1 | 34-57-21 | D00443B | | B08 | | | D41681J | | 2 | 001-099 |
| 5017R | 24 | | G2 | BS | 0-0 | 34-57-21 | D00443B | | B07 | | | D41681J | | 1 | 001-099 |
| 5017Z | | | | BS | 0-0 | 34-57-21 | D00443B | | DED | | | D41681J | | | BS 001-099 |
| FRAO | | | | | 0-0 | 34-22-91 | D45007J | | | | AO | D45007J | | 14 | 001-099 |
| FRBL | | | | | 0-0 | 34-57-21 | D41993J | | | | BL | D41993J | | 3 | 001-099 |
| FRBM | | | | | 0-0 | 34-57-21 | D41993J | | | | BM | D41993J | | 6 | 001-099 |
| FRBN | | | | | 0-0 | 34-57-21 | D41993J | | | | BN | D41993J | | 9 | 001-099 |
| FRBS | | | | | 0-0 | 34-57-21 | D41681J | | | | BS | D41681J | | 3 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1000

Page 3 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1011 | 286N1011 | | | E6-1 SHELF - LEFT | | | | | | | | | | | |
| 0001 | 24 | | GK | | 1-0 | 34-57-11 | D00245B | C09 | | | SM00001 | | WI | | 115-199 |
| 0002 | 24 | | GK | | 1-0 | 34-57-11 | D00245B | C07 | | | SM00001 | | WI | | 115-199 |
| 0003 | 24 | | GK | | 1-0 | 34-57-11 | D00245B | C05 | | | SM00001 | | WI | | 115-199 |
| 0022 | 18 | | GA | | 1-6 | 34-57-11 | D41999J | 21 | 18 | | GD01967 | ST.. | 2 | | 115-199 |
| 0026 | 20 | | GA | | 3-0 | 34-51-11 | D00231C | 3 | | | GD01963 | AC.. | 2 | | 115-199 |
| 0027 | 20 | | GA | | 3-0 | 34-51-11 | D00231C | 4 | | | GD01963 | ST.. | 2 | | 115-199 |
| 0028 | 22 | | GA | | 3-0 | 34-51-11 | D00231B | A11 | | | D41685J | 32 | | | 115-199 |
| 0029 | 22 | | GA | | 3-0 | 34-51-11 | D00231B | A15 | | | SM00002 | | WI | | 115-199 |
| 002CO | | | | AF | 0-0 | 34-51-11 | D00231C | = C1 | | | D41995J | = C1 | | | 115-199 |
| 002CX | | 66 | | AF | 1-11 | 34-51-11 | D00231C | 1 | | | D41995J | = A1 | | | 115-199 |
| 0030 | 22 | | GA | | 3-0 | 34-51-11 | SM00002 | | WI | | D41685J | 23 | | | 115-199 |
| 0031 | 20 | | GA | | 3-0 | 34-51-11 | D41685J | | | AB | GD01964 | ST.. | 2 | | 115-199 |
| 0032 | 20 | | GA | | 3-0 | 34-51-11 | D42001J | | | AC | GD01964 | ST.. | 2 | | 115-199 |
| 0033 | 20 | | GA | | 3-0 | 34-51-11 | D41685J | | | AD | GD01964 | ST.. | 2 | | 115-199 |
| 0034 | 20 | | GA | | 3-0 | 34-22-19 | D41685J | | | AE | GD01964 | ST.. | 2 | | 115-199 |
| 0035 | 22 | | GA | | 3-0 | 23-51-12 | D41685J | 6 | | | GD01964 | ST.. | 2 | | 115-199 |
| 0036 | 22 | | GA | | 3-0 | 23-51-12 | D41685J | 9 | | | GD01964 | ST.. | 2 | | 115-199 |
| 0037 | 22 | | GA | | 3-0 | 34-32-11 | D00231B | A02 | | | D42001J | 11 | | | 115-199 |
| 0038 | 22 | | GA | | 3-0 | 34-32-11 | D00231B | B02 | | | D42001J | 12 | | | 115-199 |
| 0039 | 22 | | GA | | 3-0 | 34-32-11 | D00231B | C02 | | | D42001J | 13 | | | 115-199 |
| 003CO | | | | AG | 0-0 | 34-32-11 | D00231C | = C5 | | | D41917J | = C1 | | | 115-199 |
| 003CX | | 66 | | AG | 1-5 | 34-32-11 | D00231C | 5 | | | D41917J | = A1 | | | 115-199 |
| 0040 | 22 | | GA | | 3-0 | 34-57-11 | D00245B | B15 | | | SM00002 | | WI | | 115-199 |
| 0042 | 20 | | GA | | 3-0 | 34-57-11 | D00245C | 4 | | | GD01964 | AC.. | 2 | | 115-199 |
| 0043 | 20 | | GA | | 3-0 | 34-57-11 | D00245C | 3 | | | GD01964 | ST.. | 2 | | 115-199 |
| 0044 | 20 | | GA | | 3-0 | 23-51-13 | D41685J | | | AF | GD01964 | ST.. | 2 | | 115-199 |
| 0045 | 20 | | GA | | 1-6 | 34-57-11 | D41999J | | | AG | GD01967 | ST.. | 2 | | 115-199 |
| 0046 | 20 | | GA | | 1-6 | 34-57-11 | D41999J | | | AH | GD01967 | ST.. | 2 | | 115-199 |
| 0047 | 20 | | GA | | 1-6 | 34-57-11 | D41999J | | | AI | GD01967 | ST.. | 2 | | 115-199 |
| 0048 | 20 | | GA | | 3-0 | 34-57-11 | D42005J | | | AJ | GD01964 | ST.. | 2 | | 115-199 |
| 0049 | 20 | | GA | | 3-0 | 34-22-83 | D42001J | | | AK | GD01964 | ST.. | 2 | | 115-199 |
| 0050 | 22 | | GA | | 3-0 | 34-57-11 | D00245B | C13 | | | GD01964 | DC.. | 2 | | 115-199 |
| 0051 | 22 | | GA | | 4-0 | 34-57-11 | D00245B | C12 | | | D41999J | 12 | | | 115-199 |
| 0056 | 20 | | GA | | 3-0 | 34-22-18 | D41685J | | | AM | GD01963 | ST.. | 2 | | 115-199 |
| 1001 | 22 | | GT | HG | 4-0 | 34-51-11 | D00231C | 2 | | | D41962J | 1 | | | 115-199 |
| 1001Z | | | | HG | 0-0 | 34-51-11 | D00231C | DED | | | D41962J | DED | | | 115-199 |
| 1002 | 22 | | GA | | 3-0 | 34-57-11 | D00245C | 2 | | | D42005J | 7 | | | 115-199 |
| 2002B | 22 | | GB | AH | 3-0 | 34-51-11 | D00231B | D15 | | | D42001J | 5 | | | 115-199 |
| 2002R | 22 | | GB | AH | 0-0 | 34-51-11 | D00231B | C15 | | | D42001J | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1010

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1011 | 286N1011 | | | E6-1 SHELF - LEFT (continued) | | | | | | | | | | | |
| 2003B | 24 | GL | AI | | 3-0 | 23-51-12 | D00231B | C07 | | | D41685J | 4 | | | 115-199 |
| 2003R | 24 | GL | AI | | 0-0 | 23-51-12 | D00231B | B07 | | | D41685J | 5 | | | 115-199 |
| 2004B | 24 | GL | AJ | | 3-0 | 23-51-12 | D00231B | D04 | | | D41685J | 7 | | | 115-199 |
| 2004R | 24 | GL | AJ | | 0-0 | 23-51-12 | D00231B | C04 | | | D41685J | 8 | | | 115-199 |
| 2005B | 22 | GB | AV | | 4-0 | 34-57-11 | D00245B | C11 | | | D41999J | 11 | | | 115-199 |
| 2005R | 22 | GB | AV | | 0-0 | 34-57-11 | D00245B | C10 | | | D41999J | 10 | | | 115-199 |
| 2504B | 24 | G2 | AP | | 3-0 | 23-51-13 | D00245B | B02 | | | D41685J | 10 | | | 115-199 |
| 2504R | 24 | G2 | AP | | 0-0 | 23-51-13 | D00245B | B01 | | | D41685J | 11 | | | 115-199 |
| 2504Z | | | AP | | 0-0 | 23-51-13 | D00245B | DED | | | D41685J | | | AF | 115-199 |
| 2505B | 24 | 7P | AQ | | 4-0 | 34-57-11 | D00245B | D01 | | | D41999J | 1 | | | 115-199 |
| 2505N | 24 | 7P | AQ | | 0-0 | 34-57-11 | D00245B | D02 | | | D41999J | 2 | | | 115-199 |
| 2505Z | | | AQ | | 0-0 | 34-57-11 | D00245B | DED | | | D41999J | | | AG | 115-199 |
| 2506B | 24 | 7P | AR | | 4-0 | 34-57-11 | D00245B | D07 | | | D41999J | 4 | | | 115-199 |
| 2506N | 24 | 7P | AR | | 0-0 | 34-57-11 | D00245B | D08 | | | D41999J | 5 | | | 115-199 |
| 2506Z | | | AR | | 0-0 | 34-57-11 | D00245B | DED | | | D41999J | | | AH | 115-199 |
| 2507B | 24 | 7P | AS | | 4-0 | 34-57-11 | D00245B | D14 | | | D41999J | 7 | | | 115-199 |
| 2507N | 24 | 7P | AS | | 0-0 | 34-57-11 | D00245B | D15 | | | D41999J | 8 | | | 115-199 |
| 2507Z | | | AS | | 0-0 | 34-57-11 | D00245B | DED | | | D41999J | | | AI | 115-199 |
| 5001B | 24 | G2 | AK | | 3-0 | 34-51-11 | D00231B | C09 | | | D41685J | 30 | | | 115-199 |
| 5001R | 24 | G2 | AK | | 0-0 | 34-51-11 | D00231B | B09 | | | D41685J | 29 | | | 115-199 |
| 5001Z | | | AK | | 0-0 | 34-51-11 | D00231B | DED | | | D41685J | | | AB | 115-199 |
| 5002B | 24 | G2 | AL | | 3-0 | 34-51-11 | D00231B | C11 | | | D42001J | 2 | | | 115-199 |
| 5002R | 24 | G2 | AL | | 0-0 | 34-51-11 | D00231B | B11 | | | D42001J | 1 | | | 115-199 |
| 5002Z | | | AL | | 0-0 | 34-51-11 | D00231B | DED | | | D42001J | | | AC | 115-199 |
| 5003B | 24 | G2 | AM | | 3-0 | 34-51-11 | D00231B | B04 | | | D41685J | 34 | | | 115-199 |
| 5003R | 24 | G2 | AM | | 0-0 | 34-51-11 | D00231B | A04 | | | D41685J | 33 | | | 115-199 |
| 5003Z | | | AM | | 0-0 | 34-51-11 | D00231B | DED | | | D41685J | | | AD | 115-199 |
| 5004B | 24 | G2 | AN | | 3-0 | 34-22-19 | D00231B | C13 | | | D41685J | 42 | | | 115-199 |
| 5004R | 24 | G2 | AN | | 0-0 | 34-22-19 | D00231B | B13 | | | D41685J | 41 | | | 115-199 |
| 5004Z | | | AN | | 0-0 | 34-22-19 | D00231B | DED | | | D41685J | | | AE | 115-199 |
| 5005B | 24 | G2 | AT | | 3-0 | 34-57-11 | D00245B | B08 | | | D42005J | 2 | | | 115-199 |
| 5005R | 24 | G2 | AT | | 0-0 | 34-57-11 | D00245B | B07 | | | D42005J | 1 | | | 115-199 |
| 5005Z | | | AT | | 0-0 | 34-57-11 | D00245B | DED | | | D42005J | | | AJ | 115-199 |
| 5006B | 24 | G2 | AU | | 3-0 | 34-22-83 | D00245B | B11 | | | D42001J | 7 | | | 115-199 |
| 5006R | 24 | G2 | AU | | 0-0 | 34-22-83 | D00245B | B10 | | | D42001J | 6 | | | 115-199 |
| 5006Z | | | AU | | 0-0 | 34-22-83 | D00245B | DED | | | D42001J | | | AK | 115-199 |
| 5008B | 24 | G2 | AZ | | 3-0 | 34-22-18 | D00245B | B14 | | | D41685J | 14 | | | 115-199 |
| 5008R | 24 | G2 | AZ | | 0-0 | 34-22-18 | D00245B | B13 | | | D41685J | 13 | | | 115-199 |
| 5008Z | | | AZ | | 0-0 | 34-22-18 | D00245B | DED | | | D41685J | | | AM | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1010

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|-------------|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1011 | 286N1011 | | | | E6-1 SHELF - LEFT (continued) | | | | | | | | | | |
| FRAB | | | | | 0-0 | 34-51-11 | D41685J | | | AB | D41685J | 31 | | | 115-199 |
| FRAC | | | | | 0-0 | 34-51-11 | D42001J | | | AC | D42001J | 3 | | | 115-199 |
| FRAD | | | | | 0-0 | 34-51-11 | D41685J | | | AD | D41685J | 35 | | | 115-199 |
| FRAE | | | | | 0-0 | 34-22-19 | D41685J | | | AE | D41685J | 43 | | | 115-199 |
| FRAF | | | | | 0-0 | 23-51-13 | D41685J | | | AF | D41685J | 12 | | | 115-199 |
| FRAG | | | | | 0-0 | 34-57-11 | D41999J | | | AG | D41999J | 3 | | | 115-199 |
| FRAH | | | | | 0-0 | 34-57-11 | D41999J | | | AH | D41999J | 6 | | | 115-199 |
| FRAI | | | | | 0-0 | 34-57-11 | D41999J | | | AI | D41999J | 9 | | | 115-199 |
| FRAJ | | | | | 0-0 | 34-57-11 | D42005J | | | AJ | D42005J | 3 | | | 115-199 |
| FRAK | | | | | 0-0 | 34-22-83 | D42001J | | | AK | D42001J | 8 | | | 115-199 |
| FRAM | | | | | 0-0 | 34-22-18 | D41685J | | | AM | D41685J | 15 | | | 115-199 |
| W1013 | 286N1013 | | | | E6-1 SHELF - RIGHT | | | | | | | | | | |
| 0001 | 24 | | GK | | 1-0 | 34-57-21 | D00443B | C09 | | | SM00001 | | WI | | 115-199 |
| 0002 | 24 | | GK | | 1-0 | 34-57-21 | D00443B | C07 | | | SM00001 | | WI | | 115-199 |
| 0003 | 24 | | GK | | 1-0 | 34-57-21 | D00443B | C05 | | | SM00001 | | WI | | 115-199 |
| 0022 | 18 | | GA | | 1-6 | 34-57-21 | D41993J | 21 | 18 | | GD01966 | ST.. | 2 | | 115-199 |
| 0025 | 22 | | GA | | 2-0 | 34-51-21 | D00235C | 2 | | | D41908J | 5 | | | 115-199 |
| 0026 | 20 | | GA | | 3-0 | 34-51-21 | D00235C | 3 | | | GD01966 | AC.. | 2 | | 115-199 |
| 0027 | 20 | | GA | | 3-0 | 34-51-21 | D00235C | 4 | | | GD01966 | ST.. | 2 | | 115-199 |
| 0028 | 22 | | GA | | 3-0 | 34-51-21 | D00235B | A11 | | | D41683J | 19 | | | 115-199 |
| 0029 | 22 | | GA | | 2-0 | 34-51-21 | D00235B | A15 | | | SM00002 | | WI | | 115-199 |
| 002CO | | | | AF | 0-0 | 34-51-21 | D00235C | = C1 | | | D41997J | = C1 | | | 115-199 |
| 002CX | | 66 | | AF | 1-9 | 34-51-21 | D00235C | 1 | | | D41997J | = A1 | | | 115-199 |
| 0030 | 22 | | GA | | 2-0 | 34-51-21 | SM00002 | | WI | | D41683J | 29 | | | 115-199 |
| 0031 | 20 | | GA | | 3-0 | 34-51-21 | D41683J | | | AB | GD01970 | ST.. | 2 | | 115-199 |
| 0032 | 20 | | GA | | 3-0 | 34-51-21 | D42003J | | | AC | GD01970 | ST.. | 2 | | 115-199 |
| 0033 | 20 | | GA | | 3-0 | 34-51-21 | D41683J | | | AD | GD01970 | ST.. | 2 | | 115-199 |
| 0034 | 20 | | GA | | 3-0 | 34-22-29 | D41683J | | | AE | GD01970 | ST.. | 2 | | 115-199 |
| 0035 | 20 | | GA | | 3-0 | 23-51-12 | D41683J | 5 | | | GD01970 | ST.. | 2 | | 115-199 |
| 0036 | 22 | | GA | | 3-0 | 34-51-21 | D00235B | D02 | | | GD01966 | ST.. | 2 | | 115-199 |
| 0040 | 22 | | GA | | 2-0 | 34-57-21 | D00443B | B15 | | | SM00002 | | WI | | 115-199 |
| 0042 | 20 | | GA | | 3-0 | 34-57-21 | D00443C | 4 | | | GD01966 | AC.. | 2 | | 115-199 |
| 0043 | 20 | | GA | | 3-0 | 34-57-21 | D00443C | 3 | | | GD01966 | ST.. | 2 | | 115-199 |
| 0044 | 20 | | GA | | 3-0 | 23-51-13 | D41683J | | | AF | GD01970 | ST.. | 2 | | 115-199 |
| 0045 | 20 | | GA | | 1-6 | 34-57-21 | D41993J | | | AG | GD01966 | ST.. | 2 | | 115-199 |
| 0046 | 20 | | GA | | 1-6 | 34-57-21 | D41993J | | | AH | GD01966 | ST.. | 2 | | 115-199 |
| 0047 | 20 | | GA | | 1-6 | 34-57-21 | D41993J | | | AI | GD01966 | ST.. | 2 | | 115-199 |
| 0048 | 20 | | GA | | 3-0 | 34-57-21 | D42007J | | | AJ | GD01970 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1010

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1013 | 286N1013 | | | E6-1 SHELF - RIGHT (continued) | | | | | | | | | | | |
| 0049 | 20 | | GA | | 3-0 | 34-22-93 | D42003J | | | AK | GD01970 | ST.. | 2 | | 115-199 |
| 0050 | 22 | | GA | | 3-0 | 34-57-21 | D00443B | C13 | | | GD01966 | DC.. | 2 | | 115-199 |
| 0051 | 22 | | GA | | 3-0 | 34-57-21 | D00443B | C12 | | | D41993J | 12 | | | 115-199 |
| 0175 | 20 | | GA | | 3-0 | 34-22-28 | D41683J | | | AM | GD01964 | ST.. | 2 | | 115-199 |
| 1001 | 20 | | GT | IA | 3-0 | 34-57-21 | D00443C | 2 | | | D42007J | 7 | | | 115-199 |
| 1001Z | | | | IA | 0-0 | 34-57-21 | D00443C | DED | | | D42007J | DED | | | 115-199 |
| 2002B | 22 | | GB | AH | 3-0 | 34-51-21 | D00235B | D15 | | | D42003J | 5 | | | 115-199 |
| 2002R | 22 | | GB | AH | 0-0 | 34-51-21 | D00235B | C15 | | | D42003J | 4 | | | 115-199 |
| 2003B | 24 | | GL | AI | 3-0 | 23-51-12 | D00235B | C07 | | | D41683J | 3 | | | 115-199 |
| 2003R | 24 | | GL | AI | 0-0 | 23-51-12 | D00235B | B07 | | | D41683J | 4 | | | 115-199 |
| 2005B | 22 | | GB | AV | 3-0 | 34-57-21 | D00443B | C11 | | | D41993J | 11 | | | 115-199 |
| 2005R | 22 | | GB | AV | 0-0 | 34-57-21 | D00443B | C10 | | | D41993J | 10 | | | 115-199 |
| 2504B | 24 | | G2 | AP | 3-0 | 23-51-13 | D00443B | B02 | | | D41683J | 40 | | | 115-199 |
| 2504R | 24 | | G2 | AP | 0-0 | 23-51-13 | D00443B | B01 | | | D41683J | 39 | | | 115-199 |
| 2504Z | | | | AP | 0-0 | 23-51-13 | D00443B | DED | | | D41683J | | | AF | 115-199 |
| 2505B | 24 | | 7P | AQ | 3-0 | 34-57-21 | D00443B | D01 | | | D41993J | 1 | | | 115-199 |
| 2505N | 24 | | 7P | AQ | 0-0 | 34-57-21 | D00443B | D02 | | | D41993J | 2 | | | 115-199 |
| 2505Z | | | | AQ | 0-0 | 34-57-21 | D00443B | DED | | | D41993J | | | AG | 115-199 |
| 2506B | 24 | | 7P | AR | 3-0 | 34-57-21 | D00443B | D07 | | | D41993J | 4 | | | 115-199 |
| 2506N | 24 | | 7P | AR | 0-0 | 34-57-21 | D00443B | D08 | | | D41993J | 5 | | | 115-199 |
| 2506Z | | | | AR | 0-0 | 34-57-21 | D00443B | DED | | | D41993J | | | AH | 115-199 |
| 2507B | 24 | | 7P | AS | 3-0 | 34-57-21 | D00443B | D14 | | | D41993J | 7 | | | 115-199 |
| 2507N | 24 | | 7P | AS | 0-0 | 34-57-21 | D00443B | D15 | | | D41993J | 8 | | | 115-199 |
| 2507Z | | | | AS | 0-0 | 34-57-21 | D00443B | DED | | | D41993J | | | AI | 115-199 |
| 5001B | 24 | | G2 | AK | 3-0 | 34-51-21 | D00235B | C09 | | | D41683J | 14 | | | 115-199 |
| 5001R | 24 | | G2 | AK | 0-0 | 34-51-21 | D00235B | B09 | | | D41683J | 13 | | | 115-199 |
| 5001Z | | | | AK | 0-0 | 34-51-21 | D00235B | DED | | | D41683J | | | AB | 115-199 |
| 5002B | 24 | | G2 | AL | 3-0 | 34-51-21 | D00235B | C11 | | | D42003J | 2 | | | 115-199 |
| 5002R | 24 | | G2 | AL | 0-0 | 34-51-21 | D00235B | B11 | | | D42003J | 1 | | | 115-199 |
| 5002Z | | | | AL | 0-0 | 34-51-21 | D00235B | DED | | | D42003J | | | AC | 115-199 |
| 5003B | 24 | | G2 | AM | 3-0 | 34-51-21 | D00235B | B04 | | | D41683J | 17 | | | 115-199 |
| 5003R | 24 | | G2 | AM | 0-0 | 34-51-21 | D00235B | A04 | | | D41683J | 16 | | | 115-199 |
| 5003Z | | | | AM | 0-0 | 34-51-21 | D00235B | DED | | | D41683J | | | AD | 115-199 |
| 5004B | 24 | | G2 | A4 | 3-0 | 34-22-29 | D00235B | C13 | | | D41683J | 31 | | | 115-199 |
| 5004R | 24 | | G2 | A4 | 0-0 | 34-22-29 | D00235B | B13 | | | D41683J | 30 | | | 115-199 |
| 5004Z | | | | A4 | 0-0 | 34-22-29 | D00235B | DED | | | D41683J | | | AE | 115-199 |
| 5005B | 24 | | G2 | AT | 3-0 | 34-57-21 | D00443B | B08 | | | D42007J | 2 | | | 115-199 |
| 5005R | 24 | | G2 | AT | 0-0 | 34-57-21 | D00443B | B07 | | | D42007J | 1 | | | 115-199 |
| 5005Z | | | | AT | 0-0 | 34-57-21 | D00443B | DED | | | D42007J | | | AJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1010

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1013 | 286N1013 | | | E6-1 SHELF - RIGHT (continued) | | | | | | | | | | | |
| 5006B | 24 | G2 | AU | | 3-0 | 34-22-93 | D00443B | B11 | | | D42003J | 7 | | | 115-199 |
| 5006R | 24 | G2 | AU | | 0-0 | 34-22-93 | D00443B | B10 | | | D42003J | 6 | | | 115-199 |
| 5006Z | | | AU | | 0-0 | 34-22-93 | D00443B | DED | | | D42003J | | | AK | 115-199 |
| 5008B | 24 | G2 | AZ | | 3-0 | 34-22-28 | D00443B | B14 | | | D41683J | 9 | | | 115-199 |
| 5008R | 24 | G2 | AZ | | 0-0 | 34-22-28 | D00443B | B13 | | | D41683J | 8 | | | 115-199 |
| 5008Z | | | AZ | | 0-0 | 34-22-28 | D00443B | DED | | | D41683J | | | AM | 115-199 |
| FRAB | | | | | 0-0 | 34-51-21 | D41683J | | | AB | D41683J | 15 | | | 115-199 |
| FRAC | | | | | 0-0 | 34-51-21 | D42003J | | | AC | D42003J | 3 | | | 115-199 |
| FRAD | | | | | 0-0 | 34-51-21 | D41683J | | | AD | D41683J | 18 | | | 115-199 |
| FRAE | | | | | 0-0 | 34-22-29 | D41683J | | | AE | D41683J | 32 | | | 115-199 |
| FRAF | | | | | 0-0 | 23-51-13 | D41683J | | | AF | D41683J | 38 | | | 115-199 |
| FRAG | | | | | 0-0 | 34-57-21 | D41993J | | | AG | D41993J | 3 | | | 115-199 |
| FRAH | | | | | 0-0 | 34-57-21 | D41993J | | | AH | D41993J | 6 | | | 115-199 |
| FRAI | | | | | 0-0 | 34-57-21 | D41993J | | | AI | D41993J | 9 | | | 115-199 |
| FRAJ | | | | | 0-0 | 34-57-21 | D42007J | | | AJ | D42007J | 3 | | | 115-199 |
| FRAK | | | | | 0-0 | 34-22-93 | D42003J | | | AK | D42003J | 8 | | | 115-199 |
| FRAM | | | | | 0-0 | 34-22-28 | D41683J | | | AM | D41683J | 10 | | | 115-199 |
| W1016 | 286N1016 | | | PANEL-EXTERIOR CONTROL,AFT CARGO DOOR | | | | | | | | | | | |
| 0001 | 22 | GA | | | 7-6 | 52-35-11 | S10182 | 2 | C | * | SP00186 | | 9 | | ALL |
| 0002 | 22 | GA | | | 0-7 | 52-35-11 | S10182 | 2 | C | * | S10182 | 5 | C | | ALL |
| 0003 | 22 | GA | | | 7-6 | 52-35-11 | S10182 | 6 | C | | SP00184 | | 9 | | ALL |
| 0004 | 22 | GA | | | 7-6 | 52-35-11 | S10182 | 1 | C | | SP00188 | | 9 | | ALL |
| 0007 | 18 | GA | | | 7-6 | 33-37-21 | S00429 | 2 | C | | SP00388 | | 9 | | ALL |
| 0008 | 18 | GA | | | 7-6 | 33-37-21 | S00429 | 3 | C | | SP00386 | | 9 | | ALL |
| W1017 | 286N1017 | | | E6-3 SHELF BUNDLE - L | | | | | | | | | | | |
| 0001 | 20 | GA | | | 3-0 | 23-11-11 | D00299C | 2 | | | D41974J | 1 | | | 115-199 |
| 0002 | 20 | GA | | | 3-0 | 23-11-11 | D00299C | 3 | | | D41974J | 2 | | | 115-199 |
| 0003 | 20 | GA | | | 3-0 | 23-11-11 | D00299C | 7 | | | D41974J | 3 | | | 115-199 |
| 0004 | 20 | GA | | | 2-0 | 23-11-11 | D00299C | 8 | | | GD02191 | AC.. | 2 | | 115-199 |
| 0005 | 20 | GA | | | 2-0 | 23-11-11 | D00299C | 10 | | | GD02191 | ST.. | 2 | | 115-199 |
| 0006 | 20 | GA | | | 3-0 | 23-11-11 | D00299B | | | AA | GD02191 | ST.. | 2 | | 115-199 |
| 0007 | 22 | GA | | | 3-0 | 23-51-14 | D00299B | B02 | | | D42211J | 10 | | | 115-199 |
| 0008 | 22 | GA | | | 3-0 | 23-11-11 | D41797J | 5 | | | D00299B | D05 | | | 115-199 |
| 0009 | 22 | GA | | | 3-0 | 23-11-11 | D41797J | 3 | | | D00299B | F05 | | | 115-199 |
| 0010 | 22 | GA | | | 3-0 | 23-11-11 | D41797J | 4 | | | D00299B | E05 | | | 115-199 |
| 0011 | 22 | GA | | | 3-0 | 23-11-11 | D41797J | 6 | | | D00299B | D02 | | | 115-199 |
| 0012 | 22 | GA | | | 2-0 | 23-11-11 | D41797J | 7 | | | D41799J | 7 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1010

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------|-------------|----|----|-----------------------------------|-------|----------|---------|------|-------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1017 | 286N1017 | | | E6-3 SHELF BUNDLE - L (continued) | | | | | | | | | | | | |
| 0013 | 22 | | GA | | 2-0 | 23-11-11 | D41797J | | 8 | | D41799J | | 8 | | 115-199 | |
| 0014 | 20 | | GA | | 3-0 | 23-11-11 | D00299C | | 1 | | D41799J | | 3 | | 115-199 | |
| 0015 | 20 | | GA | | 3-0 | 23-11-11 | D00299C | | 9 | | D41799J | | 6 | | 115-199 | |
| 0016 | 22 | | GA | | 3-0 | 23-11-11 | D00299B | | B05 | | D41799J | | 1 | | 115-199 | |
| 0017 | 22 | | GA | | 3-0 | 23-11-11 | D00299B | | C05 | | D41799J | | 2 | | 115-199 | |
| 0018 | 22 | | GA | | 3-0 | 23-11-11 | D00299B | | H05 | | D41799J | | 4 | | 115-199 | |
| 0019 | 22 | | GA | | 2-0 | 23-11-11 | D00299B | | C01 | | SM00001 | | | WI | 115-199 | |
| 001CO | | | | AE | 0-0 | 23-11-11 | D00299B | | = C71 | | D41807J | | = C1 | | 115-199 | |
| 001CX | | 65 | | AE | 1-3 | 23-11-11 | D00299B | | 71 | 5E | D41807J | | = A1 | | 115-199 | |
| 0020 | 20 | | GA | | 2-0 | 23-11-11 | D41799J | | 5 | | SM00001 | | | WI | 115-199 | |
| 0021 | 24 | | GK | | 2-0 | 23-51-14 | D42211J | | 9 | | SM00001 | | | WI | 115-199 | |
| 0022 | 20 | | GA | | 3-0 | 23-11-21 | D00301C | | 2 | | D41830J | | 1 | | 115-199 | |
| 0023 | 20 | | GA | | 3-0 | 23-11-21 | D00301C | | 3 | | D41830J | | 2 | | 115-199 | |
| 0024 | 20 | | GA | | 3-0 | 23-11-21 | D00301C | | 7 | | D41830J | | 3 | | 115-199 | |
| 0025 | 20 | | GA | | 3-0 | 23-11-21 | D00301C | | 8 | | GD02191 | | AC.. | 2 | 115-199 | |
| 0026 | 20 | | GA | | 3-0 | 23-11-21 | D00301C | | 10 | | GD02191 | | ST.. | 2 | 115-199 | |
| 0027 | 20 | | GA | | 3-0 | 23-11-21 | D00301B | | | AB | GD02191 | | ST.. | 2 | 115-199 | |
| 0028 | 22 | | GA | | 3-0 | 23-11-21 | D00301B | | D05 | | D41747J | | 5 | | 115-199 | |
| 0029 | 22 | | GA | | 3-0 | 23-11-21 | D00301B | | F05 | | D41747J | | 3 | | 115-199 | |
| 002CO | | | | AF | 0-0 | 23-11-21 | D00301B | | = C71 | | D41805J | | = C1 | | 115-199 | |
| 002CX | | 65 | | AF | 1-9 | 23-11-21 | D00301B | | 71 | | D41805J | | = A1 | | 115-199 | |
| 0030 | 22 | | GA | | 3-0 | 23-11-21 | D00301B | | E05 | | D41747J | | 4 | | 115-199 | |
| 0031 | 22 | | GA | | 3-0 | 23-11-21 | D00301B | | D02 | | D41747J | | 6 | | 115-199 | |
| 0032 | 22 | | GA | | 2-0 | 23-11-21 | D41747J | | 7 | | D41813J | | 7 | | 115-199 | |
| 0033 | 22 | | GA | | 2-0 | 23-11-21 | D41747J | | 8 | | D41813J | | 8 | | 115-199 | |
| 0034 | 20 | | GA | | 3-0 | 23-11-21 | D00301C | | 1 | | D41813J | | 3 | | 115-199 | |
| 0035 | 20 | | GA | | 3-0 | 23-11-21 | D00301C | | 9 | | D41813J | | 6 | | 115-199 | |
| 0036 | 22 | | GA | | 3-0 | 23-11-21 | D00301B | | B05 | | D41813J | | 1 | | 115-199 | |
| 0037 | 22 | | GA | | 3-0 | 23-11-21 | D00301B | | C05 | | D41813J | | 2 | | 115-199 | |
| 0038 | 22 | | GA | | 3-0 | 23-11-21 | D00301B | | H05 | | D41813J | | 4 | | 115-199 | |
| 0039 | 22 | | GA | | 2-0 | 23-11-21 | D00301B | | C01 | | SM00002 | | | WI | 115-199 | |
| 0040 | 20 | | GA | | 2-0 | 23-11-21 | SM00002 | | | WI | D41813J | | 5 | | 115-199 | |
| 0041 | 22 | | GA | | 3-0 | 23-11-21 | D00301B | | J05 | | GD02191 | | ST.. | 2 | 115-199 | |
| 0042 | 22 | | GA | | 3-0 | 23-11-11 | D00299B | | J05 | | GD02191 | | ST.. | 2 | 115-199 | |
| 0043 | 24 | | GK | | 2-0 | 23-51-14 | D42207J | | 9 | | SM00002 | | | WI | 115-199 | |
| 0044 | 22 | | GA | | 3-0 | 23-51-14 | D42207J | | 10 | | D00301B | | B02 | | 115-199 | |
| 2001B | 24 | | GL | AD | 3-0 | 23-21-11 | D00299B | | D03 | | D42211J | | 1 | | 115-199 | |
| 2001R | 24 | | GL | AD | 0-0 | 23-21-11 | D00299B | | C03 | | D42211J | | 2 | | 115-199 | |
| 2002B | 24 | | GL | AL | 3-0 | 23-21-11 | D42207J | | 2 | | D00301B | | D03 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1010

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1017 | 286N1017 | | | | E6-3 SHELF BUNDLE - L (continued) | | | | | | | | | | |
| 2002R | 24 | GL | AL | | 0-0 | 23-21-11 | D42207J | | 1 | | D00301B | C03 | | | 115-199 |
| 2501B | 24 | G2 | AA | | 3-0 | 23-11-11 | D41797J | | 10 | | D00299B | H03 | | | 115-199 |
| 2501R | 24 | G2 | AA | | 0-0 | 23-11-11 | D41797J | | 9 | | D00299B | G03 | | | 115-199 |
| 2501Z | | | AA | | 0-0 | 23-11-11 | D41797J | | 11 | | D00299B | | | AA | 115-199 |
| 2502B | 24 | G2 | AB | | 3-0 | 23-51-14 | D00299B | | B01 | | D42211J | 6 | | | 115-199 |
| 2502R | 24 | G2 | AB | | 0-0 | 23-51-14 | D00299B | | A01 | | D42211J | 7 | | | 115-199 |
| 2502Z | | | AB | | 0-0 | 23-51-14 | D00299B | | DED | | D42211J | 8 | | | 115-199 |
| 2503B | 24 | G2 | AC | | 3-0 | 23-51-14 | D00299B | | E01 | | D42211J | 3 | | | 115-199 |
| 2503R | 24 | G2 | AC | | 0-0 | 23-51-14 | D00299B | | D01 | | D42211J | 4 | | | 115-199 |
| 2503Z | | | AC | | 0-0 | 23-51-14 | D00299B | | DED | | D42211J | 5 | | | 115-199 |
| 2504B | 24 | G2 | AG | | 3-0 | 23-11-21 | D00301B | | H03 | | D41747J | 10 | | | 115-199 |
| 2504R | 24 | G2 | AG | | 0-0 | 23-11-21 | D00301B | | G03 | | D41747J | 9 | | | 115-199 |
| 2504Z | | | AG | | 0-0 | 23-11-21 | D00301B | | | AB | D41747J | 11 | | | 115-199 |
| 2505B | 24 | G2 | AH | | 3-0 | 23-51-14 | D42207J | | 6 | | D00301B | B01 | | | 115-199 |
| 2505R | 24 | G2 | AH | | 0-0 | 23-51-14 | D42207J | | 7 | | D00301B | A01 | | | 115-199 |
| 2505Z | | | AH | | 0-0 | 23-51-14 | D42207J | | 8 | | D00301B | DED | | | 115-199 |
| 2506B | 24 | G2 | AJ | | 3-0 | 23-51-14 | D42207J | | 3 | | D00301B | E01 | | | 115-199 |
| 2506R | 24 | G2 | AJ | | 0-0 | 23-51-14 | D42207J | | 4 | | D00301B | D01 | | | 115-199 |
| 2506Z | | | AJ | | 0-0 | 23-51-14 | D42207J | | 5 | | D00301B | DED | | | 115-199 |
| W1018 | 286N1018 | | | | CARGO COMPARTMENT DOOR LIGHTS , AFT | | | | | | | | | | |
| 0001 | 16 | GA | | | 7-0 | 33-37-21 | D41156J | | 1 | | GD00216 | AC.. | E | | ALL |
| 0002 | 16 | GA | | | 3-0 | 33-37-21 | D41156J | | 2 | | GD00214 | AC.. | E | | ALL |
| 0003 | 16 | GA | | | 5-0 | 33-37-21 | D41156J | | 3 | | SP00278 | | 9 | | ALL |
| 0004 | 16 | GA | | | 8-0 | 33-37-21 | SP00278 | | 9 | | SP00274 | | 9 | | ALL |
| 0005 | 16 | GA | | | 6-0 | 33-37-21 | SP00278 | | 9 | | SP00272 | | 9 | | ALL |
| 0006 | 16 | GA | | | 4-0 | 33-37-21 | SP00272 | | 9 | | SP00268 | | 9 | | ALL |
| 0007 | 16 | GA | | | 5-0 | 33-37-21 | SP00268 | | 9 | | SP00266 | | 9 | | ALL |
| 0008 | 16 | GA | | | 5-0 | 33-37-21 | SP00352 | | 9 | | GD00216 | AC.. | E | | ALL |
| 0009 | 22 | GA | | | 8-0 | 52-35-11 | D41156J | | 6 | | SP01718 | | 9 | | ALL |
| 0010 | 16 | GA | | | 2-0 | 33-37-21 | SP00270 | | 9 | | GD00216 | AC.. | E | | ALL |
| 0011 | 22 | GA | | | 8-0 | 52-35-11 | D41156J | | 7 | | SP01720 | | 9 | | ALL |
| 0012 | 16 | GA | | | 3-0 | 33-37-21 | SP00350 | | 9 | | GD00216 | AC.. | E | | ALL |
| 0013 | 16 | GA | | | 6-0 | 33-37-21 | SP00348 | | 9 | | GD00214 | AC.. | E | | ALL |
| 0015 | 16 | GA | | | 4-0 | 33-37-21 | SP00276 | | 9 | | GD00214 | AC.. | E | | ALL |
| A-A | | | | | 0-0 | 33-37-21 | L00390 | | WHT | | SP00266 | | 9 | | ALL |
| A-B | | | | | 0-0 | 33-37-21 | L00391 | | WHT | | SP00268 | | 9 | | ALL |
| A-C | | | | | 0-0 | 33-37-21 | L00392 | | WHT | | SP00272 | | 9 | | ALL |
| A-D | | | | | 0-0 | 33-37-21 | L00393 | | WHT | | SP00274 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11
Section W1010
Page 7
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|--------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1018 | 286N1018 | | | | CARGO COMPARTMENT DOOR LIGHTS , AFT (continued) | | | | | | | | | | | |
| A-E | | | | | 0-0 | 33-37-21 | L00394 | | WHT | | SP00278 | | 9 | | ALL | |
| B-A | | | | | 0-0 | 33-37-21 | L00390 | | BLK | | SP00352 | | 9 | | ALL | |
| B-B | | | | | 0-0 | 33-37-21 | L00391 | | BLK | | SP00270 | | 9 | | ALL | |
| B-C | | | | | 0-0 | 33-37-21 | L00392 | | BLK | | SP00350 | | 9 | | ALL | |
| B-D | | | | | 0-0 | 33-37-21 | L00393 | | BLK | | SP00348 | | 9 | | ALL | |
| B-E | | | | | 0-0 | 33-37-21 | L00394 | | BLK | | SP00276 | | 9 | | ALL | |
| C-1 | | | | | 0-0 | 52-35-11 | S10562 | | 1 | | SP01718 | | 9 | | ALL | |
| C-2 | | | | | 0-0 | 52-35-11 | S10562 | | 2 | | SP01718 | CAP | Y | | ALL | |
| C-3 | | | | | 0-0 | 52-35-11 | S10562 | | 3 | | SP01720 | | 9 | | ALL | |
| C-4 | | | | | 0-0 | 52-35-11 | S10562 | | 4 | | SP01718 | CAP | Y | | ALL | |
| C-5 | | | | | 0-0 | 52-35-11 | S10562 | | 5 | | SP01718 | CAP | Y | | ALL | |
| C-6 | | | | | 0-0 | 52-35-11 | S10562 | | 6 | | SP01718 | CAP | Y | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1010

Page 8 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1020 | 286N1020 | | | E6-2 SHELF HARNESS | | | | | | | | | | | |
| 0020 | 24 | | GK | | 1-11 | 49-61-11 | D01796B | D10 | | | GD01890 | DC.. | 2 | | 001-099 |
| 0041 | 24 | | GK | | 2-3 | 49-73-11 | D01796B | K07 | | | D41662J | 20 | | | 001-099 |
| 0042 | 24 | | GK | | 2-3 | 49-71-11 | D01796B | K04 | | | D41662J | 17 | | | 001-099 |
| 0315 | 16 | | GA | | 2-2 | 49-61-11 | D01796C | 9 | | | D41662J | 15 | | | 001-099 |
| 0316 | 16 | | GA | | 1-9 | 49-61-11 | D01796C | 11 | | | GD01890 | DC.. | 2 | | 001-099 |
| 0317 | 16 | | GA | | 1-9 | 49-61-11 | D01796C | 2 | | | GD01891 | ST.. | 2 | | 001-099 |
| 0318 | 22 | | GA | | 2-3 | 49-61-11 | D01796B | K06 | | | D41662J | 4 | | | 001-099 |
| 0319 | 22 | | GA | | 2-3 | 49-61-11 | D01796B | B08 | | | D41662J | 13 | | | 001-099 |
| 0320 | 22 | | GA | | 2-3 | 49-61-11 | D01796B | A05 | | | D41662J | 7 | | | 001-099 |
| 0321 | 22 | | GA | | 2-3 | 49-61-11 | D01796B | H08 | | | D41662J | 5 | | | 001-099 |
| 0322 | 22 | | GA | | 2-3 | 49-61-11 | D01796B | H07 | | | D41662J | 6 | | | 001-099 |
| 0323 | 22 | | GA | | 2-3 | 49-61-11 | D41662J | 12 | | | D01796B | D06 | | | 001-099 |
| 0324 | 22 | | GA | | 1-11 | 49-72-11 | D01796B | G05 | | | TB0200Y | A005 | BJ | | 001-099 |
| 0327 | 22 | | GA | | 2-3 | 24-22-41 | D01796B | J06 | | | D41662J | 1 | | | 001-099 |
| 0328 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | J10 | | | D41676J | 1 | | | 001-099 |
| 0329 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | J07 | | | D41676J | 2 | | | 001-099 |
| 0330 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | J08 | | | D41676J | 3 | | | 001-099 |
| 0331 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | C05 | | | D41676J | 4 | | | 001-099 |
| 0332 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | D11 | | | D41676J | 5 | | | 001-099 |
| 0333 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | F06 | | | D41676J | 6 | | | 001-099 |
| 0334 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | F07 | | | D41676J | 7 | | | 001-099 |
| 0335 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | B10 | | | D41676J | 8 | | | 001-099 |
| 0337 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | J04 | | | D41676J | 10 | | | 001-099 |
| 0338 | 22 | | GA | | 2-8 | 49-14-11 | D01796B | J05 | | | D41676J | 11 | | | 001-099 |
| 0339 | 22 | | GA | | 2-6 | 49-14-11 | D01796C | 4 | | | D41676J | 12 | | | 001-099 |
| 0340 | 22 | | GA | | 2-6 | 49-14-11 | D01796C | 6 | | | D41676J | 13 | | | 001-099 |
| 0341 | 22 | | GA | | 2-8 | 49-72-11 | D41662J | 9 | | | TB0200Y | A005 | BJ | | 001-099 |
| 0343 | 22 | | GA | | 2-8 | 49-61-14 | D41676J | 14 | | | D01796B | B07 | | | 001-099 |
| 0344 | 22 | | GA | | 2-2 | 49-41-11 | D01796C | 1 | | | D41662J | 22 | | | 001-099 |
| 0371 | 24 | | GK | | 2-8 | 24-27-41 | D41662J | 10 | | | TB0200A | A003 | 2 | | 001-099 |
| 0372 | 24 | | GK | | 0-7 | 24-27-41 | TB0200A | C003 | 2 | | TB0200Y | A005 | BJ | | 001-099 |
| 0450 | 24 | | GK | | 2-3 | 36-11-41 | D01796B | D03 | | | D41662J | 2 | | | 001-099 |
| 0500 | 24 | | GK | | 2-7 | 21-51-11 | D01796B | D05 | | | D42218J | 1 | | | 001-099 |
| 0510 | 22 | | GA | | 2-3 | 49-61-11 | D41662J | 16 | | | D01796B | D07 | | | 001-099 |
| 2111B | 24 | | GL | AK | 2-7 | 21-61-51 | D42208J | 2 | | | D01796B | D08 | | | 001-099 |
| 2111R | 24 | | GL | AK | 0-0 | 21-61-51 | D42208J | 1 | | | D01796B | D09 | | | 001-099 |
| 2501B | 22 | | GU | BA | 2-9 | 49-14-11 | D01796B | E04 | | | D41678J | 5 | | | 001-099 |
| 2501R | 22 | | GU | BA | 0-0 | 49-14-11 | D01796B | E05 | | | D41678J | 6 | | | 001-099 |
| 2501Z | | | | BA | 0-0 | 49-14-11 | D01796B | | | AJ | D41678J | | | AI | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | Effectivity |
|------------------------|-------------|----|----|--------------------------------|-------------|---------|-------|------|------|---------|-------|------|------|---------|--|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1020 | 286N1020 | | | E6-2 SHELF HARNESS (continued) | | | | | | | | | | | | |
| 2502B | 22 | GU | BB | 2-9 | 49-14-11 | D01796B | B03 | | | D41678J | 1 | | | 001-099 | | |
| 2502R | 22 | GU | BB | 0-0 | 49-14-11 | D01796B | B04 | | | D41678J | 2 | | | 001-099 | | |
| 2502Z | | | BB | 0-0 | 49-14-11 | D01796B | | | AJ | D41678J | | | AI | 001-099 | | |
| 2503B | 22 | GU | BC | 2-9 | 49-14-11 | D01796B | C08 | | | D41678J | 3 | | | 001-099 | | |
| 2503R | 22 | GU | BC | 0-0 | 49-14-11 | D01796B | C09 | | | D41678J | 4 | | | 001-099 | | |
| 2503Z | | | BC | 0-0 | 49-14-11 | D01796B | | | AJ | D41678J | | | AI | 001-099 | | |
| 2504B | 22 | GU | BD | 2-8 | 49-14-11 | D01796B | G08 | | | D41676J | 19 | | | 001-099 | | |
| 2504R | 22 | GU | BD | 0-0 | 49-14-11 | D01796B | G09 | | | D41676J | 20 | | | 001-099 | | |
| 2504Z | | | BD | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AG | 001-099 | | |
| 2505B | 22 | GU | BE | 2-8 | 49-14-11 | D01796B | F11 | | | D41676J | 21 | | | 001-099 | | |
| 2505R | 22 | GU | BE | 0-0 | 49-14-11 | D01796B | F08 | | | D41676J | 22 | | | 001-099 | | |
| 2505Z | | | BE | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AG | 001-099 | | |
| 2506B | 22 | GU | BF | 2-8 | 49-14-11 | D01796B | F09 | | | D41676J | 23 | | | 001-099 | | |
| 2506R | 22 | GU | BF | 0-0 | 49-14-11 | D01796B | F10 | | | D41676J | 24 | | | 001-099 | | |
| 2506Z | | | BF | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AG | 001-099 | | |
| 2507B | 22 | GU | BG | 2-8 | 49-14-11 | D01796B | H10 | | | D41676J | 25 | | | 001-099 | | |
| 2507R | 22 | GU | BG | 0-0 | 49-14-11 | D01796B | H11 | | | D41676J | 26 | | | 001-099 | | |
| 2507Z | | | BG | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AG | 001-099 | | |
| 2508B | 22 | GU | BH | 2-8 | 49-14-11 | D01796B | G06 | | | D41676J | 27 | | | 001-099 | | |
| 2508R | 22 | GU | BH | 0-0 | 49-14-11 | D01796B | G07 | | | D41676J | 28 | | | 001-099 | | |
| 2508Z | | | BH | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AG | 001-099 | | |
| 2512B | 22 | GU | BL | 2-8 | 49-14-11 | D01796B | A10 | | | D41676J | 30 | | | 001-099 | | |
| 2512R | 22 | GU | BL | 0-0 | 49-14-11 | D01796B | A11 | | | D41676J | 31 | | | 001-099 | | |
| 2512Z | | | BL | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AH | 001-099 | | |
| 2513B | 22 | GU | BM | 2-8 | 49-14-11 | D01796B | B05 | | | D41676J | 32 | | | 001-099 | | |
| 2513R | 22 | GU | BM | 0-0 | 49-14-11 | D01796B | B06 | | | D41676J | 33 | | | 001-099 | | |
| 2513Z | | | BM | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AH | 001-099 | | |
| 4251B | 22 | GW | VA | 2-9 | 49-14-11 | D01796B | A01 | | | D41678J | 8 | | | 001-099 | | |
| 4251G | 22 | GW | VA | 0-0 | 49-14-11 | D01796B | A02 | | | D41678J | 9 | | | 001-099 | | |
| 4251R | 22 | GW | VA | 0-0 | 49-14-11 | D01796B | A03 | | | D41678J | 10 | | | 001-099 | | |
| 4251Y | 22 | GW | VA | 0-0 | 49-14-11 | D01796B | A04 | | | D41678J | 11 | | | 001-099 | | |
| 4251Z | | | VA | 0-0 | 49-14-11 | D01796B | | | AJ | D41678J | | | AI | 001-099 | | |
| 4601G | 22 | DU | TP | 2-8 | 49-14-11 | D01796B | A06 | | | D41676J | 34 | TC | | 001-099 | | |
| 4601W | 22 | DU | TP | 0-0 | 49-14-11 | D01796B | A07 | | | D41676J | 35 | TD | | 001-099 | | |
| 4601Z | | | TP | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AH | 001-099 | | |
| 4602G | 22 | DU | TQ | 2-8 | 49-14-11 | D01796B | A08 | | | D41676J | 36 | TC | | 001-099 | | |
| 4602W | 22 | DU | TQ | 0-0 | 49-14-11 | D01796B | A09 | | | D41676J | 37 | TD | | 001-099 | | |
| 4602Z | | | TQ | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AH | 001-099 | | |
| 4603G | 22 | DU | TR | 2-8 | 49-14-11 | D01796B | E06 | | | D41676J | 38 | TC | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1020 | 286N1020 | | | E6-2 SHELF HARNESS (continued) | | | | | | | | | | | |
| 4603W | 22 | DU | | TR | 0-0 | 49-14-11 | D01796B | E07 | | | D41676J | 39 | TD | | 001-099 |
| 4603Z | | | | TR | 0-0 | 49-14-11 | D01796B | | | AJ | D41676J | | | AH | 001-099 |
| FRAG | | | | | 0-0 | 49-14-11 | D41676J | 29 | | | D41676J | | | AG | 001-099 |
| FRAH | | | | | 0-0 | 49-14-11 | D41676J | 40 | | | D41676J | | | AH | 001-099 |
| FRAI | | | | | 0-0 | 49-14-11 | D41678J | 7 | | | D41678J | | | AI | 001-099 |
| FRAJ | | | | | 0-0 | 49-14-11 | D01796B | J09 | | | D01796B | | | AJ | 001-099 |
| W1024 | 286N1024 | | | E6 RELAY PANEL HARNESS | | | | | | | | | | | |
| 0001 | 16 | GA | | | 1-11 | 49-61-11 | D42238J | 7 | | | R00011 | A | \$ | | 001-099 |
| 0001 | 16 | GA | | | 3-0 | 49-61-11 | D42238J | 14 | | | R00011 | A | \$ | | 115-199 |
| 0002 | 22 | GA | | | 2-3 | 28-25-21 | D42238J | 3 | | | D02414 | 7 | | | 001-099 |
| 0002 | 20 | GA | | | 3-0 | 28-25-21 | D42238J | 3 | | | D02414 | 7 | | | 115-199 |
| 0003 | 22 | GA | | | 2-7 | 49-41-11 | D03084 | X2 | | | TB0037Y | C009 | BJ | | 001-099 |
| 0003 | 22 | GA | | | 2-0 | 49-41-11 | D03084 | X2 | | | TB0037Y | C009 | BJ | | 115-199 |
| 0004 | 20 | GA | | | 2-0 | 33-37-21 | D04172 | B1 | | | TB0037Y | C024 | BJ | | 115-199 |
| 0005 | 20 | GA | | | 3-0 | 33-37-21 | D04172 | B2 | | | D41932J | 15 | | | 115-199 |
| 0006 | 22 | GA | | | 3-0 | 33-37-21 | D04172 | X2 | | | D42216J | 2 | | | 115-199 |
| 0007 | 22 | GA | | | 2-0 | 33-37-21 | D04172 | X1 | | | TB0037Y | A024 | BJ | | 115-199 |
| 0008 | 20 | GA | | | 3-0 | 33-37-21 | D04172 | A1 | | | T10002 | HV2 | E | | 115-199 |
| 0009 | 20 | GA | | | 3-0 | 24-32-41 | D04834 | C2 | | | TB0037Y | A030 | BJ | | 115-199 |
| 0010 | 20 | GA | | | 3-0 | 24-32-41 | D42050J | 27 | | | D04834 | A2 | | | 115-199 |
| 0011 | 16 | GA | | | 2-0 | 49-61-11 | D40170J | 14 | | | R00011 | C | E | * | ALL |
| 0012 | 22 | GA | | | 2-0 | 49-61-11 | D41680J | 6 | | | TB0037C | C001 | 2 | | 001-099 |
| 0012 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 6 | | | TB0037C | C001 | 2 | | 115-199 |
| 0013 | 22 | GA | | | 1-5 | 49-61-11 | TB0037Z | 27 | BJ | | TB0037Y | C005 | BJ | | 001-099 |
| 0013 | 20 | GA | | | 2-0 | 49-61-11 | TB0037Z | 27 | BJ | | TB0037Y | C005 | BJ | | 115-199 |
| 0014 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 20 | | | TB0037Y | A006 | BJ | | 115-199 |
| 0015 | 24 | GK | | | 3-0 | 21-51-11 | D04790 | 3 | | | D41845J | 51 | | | 115-199 |
| 0016 | 20 | GA | | | 3-0 | 24-32-41 | D42050J | 28 | | | D04834 | B2 | | | 115-199 |
| 0017 | 24 | GK | | | 2-10 | 28-25-11 | D02378 | C2 | | | D42238J | 8 | | | 001-099 |
| 0017 | 24 | GK | | | 3-0 | 28-25-11 | D02378 | C2 | | | D42238J | 8 | | | 115-199 |
| 0018 | 20 | GA | | | 2-10 | 28-25-11 | D02378 | C1 | | | D42238J | 12 | | | 001-099 |
| 0018 | 20 | GA | | | 3-0 | 28-25-11 | D02378 | C1 | | | D42238J | 12 | | | 115-199 |
| 0019 | 22 | GA | | | 1-10 | 49-61-11 | D41680J | 51 | | | TB0037Y | C005 | BJ | | 001-099 |
| 0019 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 51 | | | TB0037Y | C005 | BJ | | 115-199 |
| 0020 | 22 | GA | | | 2-7 | 49-61-11 | D02378 | A2 | | | TB0037Y | C010 | BJ | | 001-099 |
| 0020 | 22 | GA | | | 2-0 | 49-61-11 | D02378 | A2 | | | TB0037Y | C010 | BJ | | 115-199 |
| 0021 | 22 | GA | | | 2-10 | 49-61-11 | D02378 | A1 | | | TB0037Y | A004 | BJ | | 001-099 |
| 0021 | 22 | GA | | | 2-0 | 49-61-11 | D02378 | A1 | | | TB0037Y | A004 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286N1024 | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | | |
| 0022 | 22 | GA | | | 2-7 | 49-61-11 | D02378 | X2 | | | TB0037Y | C010 | BJ | | 001-099 |
| 0022 | 22 | GA | | | 2-0 | 49-61-11 | D02378 | X2 | | | TB0037Y | C010 | BJ | | 115-199 |
| 0023 | 20 | GA | | | 3-0 | 33-37-21 | D41932J | 14 | | | TB0037Y | C024 | BJ | | 115-199 |
| 0024 | 22 | GA | | | 2-0 | 49-61-11 | D41680J | 18 | | | TB0037Y | A004 | BJ | | 001-099 |
| 0024 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 18 | | | TB0037Y | A004 | BJ | | 115-199 |
| 0025 | 22 | GA | | | 2-0 | 49-61-11 | D02380 | X1 | | | TB0037Z | 27 | BJ | | ALL |
| 0026 | 22 | GA | | | 2-4 | 49-61-11 | D02380 | X2 | | | TB0037Y | A004 | BJ | | 001-099 |
| 0026 | 22 | GA | | | 2-0 | 49-61-11 | D02380 | X2 | | | TB0037Y | A004 | BJ | | 115-199 |
| 0027 | 20 | GA | | | 3-0 | 24-32-41 | D42050J | 25 | | | TB0037Y | A030 | BJ | | 115-199 |
| 0028 | 22 | GA | | | 1-9 | 49-61-11 | D41680J | 13 | | | TB0037Y | A010 | BJ | | 001-099 |
| 0028 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 13 | | | TB0037Y | A010 | BJ | | 115-199 |
| 0029 | 22 | GA | | | 1-10 | 49-61-11 | D41680J | 8 | | | TB0037Y | C005 | BJ | | 001-099 |
| 0029 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 8 | | | TB0037Y | C005 | BJ | | 115-199 |
| 0030 | 24 | GK | | | 3-0 | 24-32-41 | D42050J | 20 | | | TB0037Y | A036 | BJ | | 115-199 |
| 0031 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 10 | | | TB0037Y | A006 | BJ | | 115-199 |
| 0032 | 22 | GA | | | 1-8 | 49-61-11 | TB0037Z | 27 | BJ | | D41680J | 11 | | | 001-099 |
| 0032 | 22 | GA | | | 3-0 | 49-61-11 | D02436 | A2 | | | D41680J | 11 | | | 115-199 |
| 0033 | 22 | GA | | | 2-0 | 49-61-11 | D02436 | A1 | | | TB0037Y | A006 | BJ | | 115-199 |
| 0034 | 22 | GA | | | 2-0 | 49-61-11 | D02436 | X2 | | | TB0037Y | A006 | BJ | | 115-199 |
| 0035 | 22 | GA | | | 2-0 | 49-61-11 | D02436 | X1 | | | TB0037Z | 27 | BJ | | 115-199 |
| 0036 | 22 | GA | | | 2-0 | 49-61-11 | D41680J | 12 | | | TB0037C | C001 | 2 | | 001-099 |
| 0036 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 12 | | | TB0037C | C001 | 2 | | 115-199 |
| 0037 | 22 | GA | | | 1-8 | 49-61-11 | D02434 | A3 | | | D02378 | X1 | | | 001-099 |
| 0037 | 22 | GA | | | 2-0 | 49-61-11 | D02434 | A3 | | | D02378 | X1 | | | 115-199 |
| 0038 | 24 | GK | | | 2-0 | 24-32-41 | K10010 | X1 | C | | D03084 | C1 | | | 115-199 |
| 0039 | 22 | GA | | | 1-8 | 49-61-11 | D02434 | B3 | | | D02378 | A3 | | | 001-099 |
| 0039 | 22 | GA | | | 2-0 | 49-61-11 | D02434 | B3 | | | D02378 | A3 | | | 115-199 |
| 0040 | 22 | GA | | | 2-6 | 49-61-11 | D02434 | B2 | | | TB0037Y | A003 | BJ | | 001-099 |
| 0040 | 22 | GA | | | 2-0 | 49-61-11 | D02434 | B2 | | | TB0037Y | A003 | BJ | | 115-199 |
| 0041 | 22 | GA | | | 2-2 | 49-61-11 | D02434 | B1 | | | GD01880 | DC.. | 2 | | 001-099 |
| 0041 | 22 | GA | | | 2-0 | 49-61-11 | D02434 | B1 | | | GD01880 | DC.. | 2 | | 115-199 |
| 0042 | 20 | GA | | | 3-0 | 24-32-41 | D42050J | 21 | | | D04834 | A1 | | | 115-199 |
| 0043 | 20 | GA | | | 3-0 | 24-32-41 | D42050J | 23 | | | D04834 | C1 | | | 115-199 |
| 0044 | 20 | GA | | | 3-0 | 24-32-41 | D42050J | 22 | | | D04834 | B1 | | | 115-199 |
| 0045 | 20 | GA | | | 2-11 | 24-32-41 | GD01880 | DC.. | 2 | | K10010 | 12 | C | | 001-099 |
| 0045 | 22 | GA | | | 3-0 | 49-61-11 | D02434 | X2 | | | D41680J | 19 | | | 115-199 |
| 0046 | 22 | GA | | | 2-2 | 49-61-11 | D02434 | X1 | | | TB0037Y | A016 | BJ | | 001-099 |
| 0046 | 22 | GA | | | 2-0 | 49-61-11 | D02434 | X1 | | | TB0037Y | A012 | BJ | | 115-199 |
| 0047 | 22 | GA | | | 2-0 | 49-61-11 | D41680J | 14 | | | TB0037Y | A003 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286N1024 | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | | |
| 0047 | 22 | | GA | | 3-0 | 49-61-11 | D41680J | 14 | | | TB0037Y | A003 | BJ | | 115-199 |
| 0048 | 22 | | GA | | 2-4 | 49-61-11 | D41680J | 9 | | | D02434 | A2 | | | 001-099 |
| 0048 | 22 | | GA | | 3-0 | 49-61-11 | D41680J | 9 | | | D02434 | A2 | | | 115-199 |
| 0049 | 16 | | GA | | 0-11 | 49-61-11 | R00012 | C | E | * | R00011 | C | E | * | 001-099 |
| 0049 | 16 | | GA | | 0-7 | 49-61-11 | R00012 | C | E | * | R00011 | C | E | * | 115-199 |
| 0050 | 16 | | GA | | 2-4 | 49-61-11 | D42050J | 8 | | | R00012 | A | \$ | | 001-099 |
| 0050 | 16 | | GA | | 3-0 | 49-61-11 | D42050J | 8 | | | R00012 | A | \$ | | 115-199 |
| 0051 | 20 | | GA | | 2-8 | 49-61-11 | D42050J | 16 | | | TB0037Z | 27 | BJ | | 001-099 |
| 0051 | 20 | | GA | | 3-0 | 49-61-11 | D42050J | 16 | | | TB0037Z | 27 | BJ | | 115-199 |
| 0052 | 20 | | GA | | 3-0 | 33-37-21 | D42038J | 7 | | | TB0037Y | A024 | BJ | | 115-199 |
| 0053 | 22 | | GA | | 3-0 | 24-32-41 | D04832 | 4 | | | TB0037Y | A030 | BJ | | 115-199 |
| 0054 | 24 | | GK | | 0-7 | 24-33-12 | D04774 | A2 | | | D04774 | X2 | | | 001-099 |
| 0055 | 24 | | GK | | 1-4 | 28-25-21 | D02378 | B3 | | | D41770J | 3 | | | 001-099 |
| 0055 | 24 | | GK | | 3-0 | 28-25-21 | D02378 | B3 | | | D41770J | 3 | | | 115-199 |
| 0056 | 24 | | GK | | 2-9 | 24-33-12 | D42238J | 5 | | | D04774 | A1 | | | 001-099 |
| 0057 | 24 | | GK | | 1-4 | 28-25-21 | D02378 | B1 | | | D41770J | 4 | | | 001-099 |
| 0057 | 24 | | GK | | 3-0 | 28-25-21 | D02378 | B1 | | | D41770J | 4 | | | 115-199 |
| 0058 | 24 | | GK | | 2-5 | 28-25-21 | D02414 | 2 | | | D41770J | 1 | | | 001-099 |
| 0058 | 24 | | GK | | 3-0 | 28-25-21 | D02414 | 2 | | | D41770J | 1 | | | 115-199 |
| 0059 | 24 | | GK | | 2-10 | 24-33-12 | D04774 | A3 | | | D42178J | 5 | | | 001-099 |
| 0060 | 24 | | GK | | 2-10 | 24-33-12 | D04774 | B1 | | | D42178J | 11 | | | 001-099 |
| 0061 | 24 | | GK | | 2-9 | 24-33-12 | D04774 | X1 | | | TB0037Y | C029 | BJ | | 001-099 |
| 0062 | 22 | | GA | | 1-11 | 28-25-21 | D02414 | 3 | | | GD01880 | DC.. | 2 | | 001-099 |
| 0062 | 24 | | GK | | 2-0 | 28-25-21 | D02414 | 3 | | | GD01880 | DC.. | 2 | | 115-199 |
| 0063 | 24 | | GK | | 1-3 | 28-25-21 | D02414 | 5 | | | D02410 | 7 | | | 001-099 |
| 0063 | 24 | | GK | | 2-0 | 28-25-21 | D02414 | 5 | | | D02410 | 7 | | | 115-199 |
| 0064 | 24 | | GK | | 1-11 | 28-25-21 | D02410 | 3 | | | GD01880 | DC.. | 2 | | 001-099 |
| 0064 | 24 | | GK | | 2-0 | 28-25-21 | D02410 | 3 | | | GD01880 | DC.. | 2 | | 115-199 |
| 0065 | 24 | | GK | | 2-1 | 24-33-12 | D42178J | 4 | | | TB0037Y | C029 | BJ | | 001-099 |
| 0066 | 24 | | GK | | 2-2 | 24-33-12 | D05025 | A3 | | | D42178J | 1 | | | 001-099 |
| 0067 | 24 | | GK | | 2-4 | 24-33-12 | D42050J | 15 | | | D05025 | X1 | | | 001-099 |
| 0068 | 24 | | GK | | 2-1 | 24-33-12 | D42238J | 6 | | | D42178J | 12 | | | 001-099 |
| 0069 | 24 | | GK | | 2-1 | 24-33-12 | D42238J | 9 | | | D42178J | 7 | | | 001-099 |
| 0070 | 24 | | GK | | 2-1 | 24-33-12 | D42238J | 10 | | | D42178J | 10 | | | 001-099 |
| 0071 | 24 | | GK | | 1-10 | 24-33-12 | D41680J | 27 | | | D42178J | 9 | | | 001-099 |
| 0072 | 20 | | GA | | 2-8 | 28-25-11 | D02378 | D2 | | | D41680J | 46 | | | 001-099 |
| 0072 | 20 | | GA | | 3-0 | 28-25-11 | D02378 | D2 | | | D41855J | 18 | | | 115-199 |
| 0073 | 22 | | GA | | 7-8 | 49-41-11 | K00117 | X2 | E | | GD03910 | DC.. | E | | 001-099 |
| 0073 | 22 | | GA | | 8-0 | 49-41-11 | K00117 | X2 | E | | GD02610 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | | 286N1024 | | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | |
| 0074 | 22 | GA | | | 2-2 | 49-41-11 | D03084 | A1 | | | K00117 | X1 | E | | 001-099 |
| 0074 | 22 | GA | | | 4-0 | 49-41-11 | D03084 | A1 | | | K00117 | X1 | E | | 115-199 |
| 0075 | 22 | GA | | | 2-3 | 49-41-11 | D02416 | A3 | | | D03084 | A2 | | | 001-099 |
| 0075 | 22 | GA | | | 3-0 | 49-41-11 | D03084 | A2 | | | D02416 | A3 | | | 115-199 |
| 0076 | 22 | GA | | | 2-0 | 49-41-11 | D02416 | A2 | | | TB0037Z | 27 | BJ | | ALL |
| 0077 | 24 | GK | | | 1-11 | 24-33-12 | D41680J | 22 | | | TB0037Y | C029 | BJ | | 001-099 |
| 0078 | 22 | GA | | | 2-0 | 49-41-11 | D02416 | X2 | | | GD01881 | AC.. | 2 | | ALL |
| 0079 | 18 | GA | | | 2-8 | 49-61-14 | D02380 | B3 | | | D41688J | 1 | | | 001-099 |
| 0079 | 18 | GA | | | 3-0 | 49-61-14 | D02380 | B3 | | | D41688J | 1 | | | 115-199 |
| 0080 | 18 | GA | | | 2-8 | 49-61-14 | D02380 | B1 | | | D41688J | 2 | | | 001-099 |
| 0080 | 18 | GA | | | 3-0 | 49-61-14 | D02380 | B1 | | | D41688J | 2 | | | 115-199 |
| 0081 | 18 | GA | | | 2-5 | 49-61-14 | D02380 | B2 | | | D42050J | 6 | | | 001-099 |
| 0081 | 18 | GA | | | 3-0 | 49-61-14 | D02380 | B2 | | | D42050J | 6 | | | 115-199 |
| 0082 | 24 | GK | | | 2-0 | 24-33-12 | D41680J | 16 | | | TB0037Y | C003 | BJ | | 001 |
| 0082 | 24 | GK | | | 2-2 | 24-33-12 | TB0037Y | C003 | BJ | | D07678 | X2 | | | 002-008, 010-099 |
| 0082 | 24 | GK | | | 2-0 | 24-33-12 | TB0037Y | C003 | BJ | | D41680J | 16 | | | 009 |
| 0083 | 24 | GK | | | 2-10 | 24-34-11 | D41680J | 17 | | | D42050J | 3 | | | 001-099 |
| 0083 | 22 | GA | | | 4-0 | 24-34-11 | D41680J | 17 | | | D42050J | 3 | | | 115-199 |
| 0084 | 24 | GK | | | 2-9 | 24-33-12 | D42238J | 2 | | | D03084 | D2 | | | 001-099 |
| 0085 | 22 | GA | | | 2-6 | 49-41-11 | D03084 | X1 | | | TB0037Z | 27 | BJ | | 001-099 |
| 0085 | 22 | GA | | | 2-0 | 49-41-11 | D03084 | X1 | | | TB0037Z | 27 | BJ | | 115-199 |
| 0086 | 22 | GA | | | 2-0 | 49-61-11 | D41680J | 7 | | | TB0037C | A001 | 2 | | 001-099 |
| 0086 | 22 | GA | | | 3-0 | 49-61-11 | D41680J | 7 | | | TB0037C | A001 | 2 | | 115-199 |
| 0087 | 22 | GA | | | 1-2 | 49-41-11 | D02416 | X1 | | | D04832 | 2 | | | 001-099 |
| 0087 | 22 | GA | | | 2-0 | 49-41-11 | D02416 | X1 | | | D04832 | 2 | | | 115-199 |
| 0088 | 24 | GK | | | 2-10 | 24-33-12 | D03084 | D3 | | | D42178J | 8 | | | 001-099 |
| 0089 | 22 | GA | | | 2-6 | 24-31-41 | D03084 | B2 | | | GD01880 | DC.. | 2 | | 001-099 |
| 0089 | 22 | GA | | | 2-0 | 24-31-41 | D03084 | B2 | | | GD01880 | DC.. | 2 | | 115-199 |
| 0090 | 24 | GK | | | 2-3 | 24-31-41 | D02416 | B2 | | | TB0037B | C031 | 2 | | 001-099 |
| 0090 | 24 | GK | | | 2-0 | 24-31-41 | D02416 | B2 | | | TB0037B | C031 | 2 | | 115-199 |
| 0091 | 24 | GK | | | 1-11 | 24-32-41 | D03084 | C1 | | | K10010 | X1 | C | | 001-099 |
| 0091 | 20 | GA | | | 3-0 | 24-32-41 | K10010 | 12 | C | | GD01880 | DC.. | 2 | | 115-199 |
| 0092 | 20 | GA | | | 2-11 | 24-32-41 | K10010 | 11 | C | * | D04834 | X2 | | | 001-099 |
| 0092 | 24 | GK | | | 3-0 | 24-32-41 | D40170J | 2 | | | D04834 | X1 | | *1 | 115-199 |
| 0093 | 20 | GA | | | 2-11 | 24-32-41 | K10010 | 11 | C | * | D04834 | D2 | | | 001-099 |
| 0093 | 24 | GK | | | 3-0 | 24-32-41 | D04832 | 7 | | | D04834 | X1 | | *1 | 115-199 |
| 0094 | 22 | GA | | | 2-9 | 49-72-11 | D42050J | 18 | | | TB0037Y | A010 | BJ | | 001-099 |
| 0094 | 22 | GA | | | 3-0 | 49-72-11 | D42050J | 18 | | | TB0037Y | A010 | BJ | | 115-199 |
| 0095 | 24 | GK | | | 2-0 | 24-33-12 | D41680J | 45 | | | D05025 | A2 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286N1024 | | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | | |
| 0096 | 20 | | GA | | 2-4 | 24-32-41 | | TB0037Y | A030 | BJ | | D04834 | | C2 | | 001-099 |
| 0097 | 20 | | GA | | 2-10 | 28-25-11 | | D02378 | | D1 | | D42238J | | 11 | | 001-099 |
| 0097 | 20 | | GA | | 3-0 | 28-25-11 | | D02378 | | D1 | | D41855J | | 51 | | 115-199 |
| 0098 | 22 | | GA | | 1-3 | 49-61-11 | | TB0037Y | C010 | BJ | | TB0037C | A001 | 2 | | 001-099 |
| 0098 | 22 | | GA | | 2-0 | 49-61-11 | | TB0037Y | C010 | BJ | | TB0037C | A001 | 2 | | 115-199 |
| 0099 | 22 | | GA | | 1-9 | 49-72-11 | | D41680J | | 24 | | TB0037Y | A010 | BJ | | 001-099 |
| 0099 | 22 | | GA | | 3-0 | 49-72-11 | | D41680J | | 24 | | TB0037Y | A010 | BJ | | 115-199 |
| 0100 | 22 | | GA | | 2-3 | 49-41-11 | | D02416 | | A1 | | D03084 | | C2 | | 001-099 |
| 0100 | 22 | | GA | | 3-0 | 49-41-11 | | D03084 | | C2 | | D02416 | | A1 | | 115-199 |
| 0101 | 24 | | GK | | 1-9 | 24-33-12 | | D42238J | | 1 | | TB0037Y | A029 | BJ | | 001-099 |
| 0102 | 24 | | GK | | 2-2 | 24-33-12 | | D03084 | | B1 | | D05025 | | X2 | | 001-099 |
| 0103 | 22 | | GA | | 2-2 | 24-32-41 | | D04832 | | 4 | | TB0037Y | A030 | BJ | | 001-099 |
| 0103 | 20 | | GA | | 3-0 | 24-32-41 | | D42050J | | 24 | | D04834 | | D1 | | 115-199 |
| 0104 | 24 | | GK | | 0-7 | 24-31-41 | | TB0037Y | A029 | BJ | | TB0037B | A031 | 2 | | 001-099 |
| 0104 | 24 | | GK | | 2-0 | 24-31-41 | | TB0037Y | A029 | BJ | | TB0037B | A031 | 2 | | 115-199 |
| 0105 | 22 | | GA | | 3-0 | 49-94-11 | | D41680J | | 25 | | D41688J | | 13 | | 001-099 |
| 0105 | 22 | | GA | | 2-0 | 49-94-14 | | D41680J | | 25 | | D41688J | | 13 | | 115-199 |
| 0106 | 22 | | GA | | 2-0 | 49-94-14 | | D41680J | | 26 | | D41688J | | 14 | | 115-199 |
| 0107 | 22 | | GA | | 2-0 | 49-94-14 | | D41680J | | 28 | | D41688J | | 15 | | 115-199 |
| 0108 | 20 | | GA | | 3-0 | 33-37-21 | | D04172 | | A2 | | D42038J | | 3 | | 115-199 |
| 0109 | 20 | | GA | | 2-11 | 24-32-41 | | D42050J | | 25 | | TB0037Y | A030 | BJ | | 001-099 |
| 0110 | 24 | | GK | | 2-11 | 24-31-41 | | D42050J | | 26 | | TB0037Y | A029 | BJ | | 001-099 |
| 0110 | 24 | | GK | | 3-0 | 24-31-41 | | D42050J | | 26 | | TB0037Y | A029 | BJ | | 115-199 |
| 0111 | 20 | | GA | | 2-8 | 24-32-41 | | D42050J | | 28 | | D04834 | | B2 | | 001-099 |
| 0111 | 20 | | GA | | 3-0 | 24-32-41 | | K10010 | | 11 | C | D04834 | | D2 | | 115-199 |
| 0112 | 20 | | GA | | 2-8 | 24-32-41 | | D42050J | | 27 | | D04834 | | A2 | | 001-099 |
| 0112 | 20 | | GA | | 3-0 | 24-32-41 | | K10010 | | 11 | C | D04834 | | X2 | | 115-199 |
| 0113 | 24 | | GK | | 3-0 | 24-32-41 | | TB0037Y | A036 | BJ | | D42050J | | 20 | | 001-099 |
| 0113 | 24 | | GK | | 2-0 | 21-51-11 | | D04790 | | 7 | | TB0037Y | A012 | BJ | | 115-199 |
| 0114 | 20 | | GA | | 2-8 | 24-32-41 | | D42050J | | 21 | | D04834 | | A1 | | 001-099 |
| 0114 | 24 | | GK | | 2-0 | 21-51-11 | | D04790 | | 2 | | TB0037Y | A012 | BJ | | 115-199 |
| 0115 | 20 | | GA | | 2-8 | 24-32-41 | | D42050J | | 22 | | D04834 | | B1 | | 001-099 |
| 0115 | 24 | | GK | | 3-0 | 21-51-11 | | D04790 | | 5 | | D41845J | | 52 | | 115-199 |
| 0116 | 20 | | GA | | 2-8 | 24-32-41 | | D42050J | | 23 | | D04834 | | C1 | | 001-099 |
| 0116 | 22 | | GA | | 2-0 | 49-61-11 | | TB0037Y | A012 | BJ | | TB0037Z | | 27 | BJ | 115-199 |
| 0117 | 22 | | GA | | 2-0 | 49-61-11 | | D02436 | | B2 | | TB0037Y | A010 | BJ | | 115-199 |
| 0118 | 22 | | GA | | 1-10 | 49-61-11 | | D41680J | | 39 | | TB0037Y | C005 | BJ | | 001-099 |
| 0118 | 22 | | GA | | 3-0 | 49-61-11 | | D41680J | | 39 | | TB0037Y | C005 | BJ | | 115-199 |
| 0119 | 24 | | GK | | 3-0 | 21-51-14 | | D41845J | | 35 | | TB0037Z | | 17 | BJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | | 286N1024 | | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | |
| 0120 | 24 | GK | | | 2-2 | 49-61-14 | D41680J | 53 | | | D02380 | A2 | | | 001-099 |
| 0120 | 24 | GK | | | 3-0 | 49-61-14 | D41680J | 53 | | | D02380 | A2 | | | 115-199 |
| 0121 | 24 | GK | | | 3-0 | 21-51-12 | D41845J | 53 | | | TB0037Y | A013 | BJ | | 115-199 |
| 0122 | 24 | GK | | | 3-0 | 21-51-12 | D02950 | C1 | | | D41845J | 20 | | | 115-199 |
| 0123 | 24 | GK | | | 3-0 | 21-51-12 | D02950 | B1 | | | D41845J | 23 | | | 115-199 |
| 0124 | 24 | GK | | | 3-0 | 21-51-12 | D02950 | A1 | | | D41845J | 24 | | | 115-199 |
| 0125 | 24 | GK | | | 2-0 | 21-51-12 | D04052 | 6 | | | TB0037Y | A013 | BJ | | 115-199 |
| 0126 | 24 | GK | | | 3-0 | 21-51-12 | D02948 | C1 | | | D41845J | 6 | | | 115-199 |
| 0127 | 24 | GK | | | 3-0 | 21-51-12 | D02948 | B1 | | | D41845J | 7 | | | 115-199 |
| 0128 | 24 | GK | | | 3-0 | 21-51-12 | D02948 | A1 | | | D41845J | 8 | | | 115-199 |
| 0129 | 24 | GK | | | 3-0 | 21-51-12 | D04052 | 1 | | | D41845J | 9 | | | 115-199 |
| 0130 | 24 | GK | | | 2-0 | 21-51-12 | D04052 | 12 | | | TB0037Y | C013 | BJ | | 115-199 |
| 0131 | 24 | GK | | | 3-0 | 21-51-12 | D02950 | X1 | | | TB0037Y | A013 | BJ | | 115-199 |
| 0132 | 24 | GK | | | 2-0 | 21-51-12 | D04052 | 13 | | | GD01880 | DC.. | 2 | | 115-199 |
| 0133 | 24 | GK | | | 3-0 | 21-51-12 | D02948 | X1 | | | TB0037Y | A013 | BJ | | 115-199 |
| 0134 | 24 | GK | | | 3-0 | 21-51-13 | D02950 | D2 | | | TB0037Z | 17 | BJ | | 115-199 |
| 0135 | 24 | GK | | | 3-0 | 21-51-13 | D02950 | D3 | | | D42212J | 7 | | | 115-199 |
| 0136 | 22 | GA | | | 3-0 | 21-51-13 | D02950 | C3 | | | D02970 | A2 | | | 115-199 |
| 0137 | 24 | GK | | | 2-0 | 21-51-13 | D02970 | A1 | | | TB0037Z | 17 | BJ | | 115-199 |
| 0138 | 24 | GK | | | 3-0 | 21-51-13 | D02970 | X2 | | | D41845J | 13 | | | 115-199 |
| 0139 | 24 | GK | | | 3-0 | 21-51-13 | D02970 | X1 | | | TB0037Z | 18 | BJ | | 115-199 |
| 0140 | 24 | GK | | | 2-0 | 21-51-13 | D02972 | A1 | | | TB0037Z | 17 | BJ | | 115-199 |
| 0141 | 24 | GK | | | 2-0 | 21-51-13 | D02972 | X1 | | | TB0037Z | 18 | BJ | | 115-199 |
| 0142 | 24 | GK | | | 3-0 | 21-51-13 | D02972 | X2 | | | D41845J | 14 | | | 115-199 |
| 0143 | 22 | GA | | | 3-0 | 21-51-13 | D02950 | B3 | | | D02972 | A2 | | | 115-199 |
| 0144 | 22 | GA | | | 3-0 | 21-51-13 | D02950 | A3 | | | D02974 | A2 | | | 115-199 |
| 0145 | 24 | GK | | | 2-0 | 21-51-13 | D02974 | A1 | | | TB0037Z | 17 | BJ | | 115-199 |
| 0146 | 24 | GK | | | 3-0 | 21-51-13 | D02974 | X2 | | | D41845J | 15 | | | 115-199 |
| 0147 | 24 | GK | | | 2-0 | 21-51-13 | D02974 | X1 | | | TB0037Z | 18 | BJ | | 115-199 |
| 0148 | 20 | GA | | | 2-8 | 24-32-41 | D42050J | 24 | | | D04834 | D1 | | | 001-099 |
| 0149 | 24 | GK | | | 3-0 | 21-51-13 | D02948 | D3 | | | TB0037Y | A014 | BJ | | 115-199 |
| 0150 | 22 | GA | | | 3-0 | 21-51-13 | D02948 | C3 | | | D02976 | A2 | | | 115-199 |
| 0152 | 24 | GK | | | 2-0 | 21-51-13 | D02976 | A1 | | | TB0037Z | 17 | BJ | | 115-199 |
| 0153 | 24 | GK | | | 2-0 | 21-51-13 | D02976 | X1 | | | TB0037Z | 18 | BJ | | 115-199 |
| 0154 | 24 | GK | | | 3-0 | 21-51-13 | D02976 | X2 | | | D41845J | 16 | | | 115-199 |
| 0155 | 24 | GK | | | 2-0 | 21-51-13 | D02978 | A1 | | | TB0037Z | 17 | BJ | | 115-199 |
| 0156 | 22 | GA | | | 3-0 | 21-51-13 | D02948 | B3 | | | D02978 | A2 | | | 115-199 |
| 0157 | 24 | GK | | | 2-0 | 21-51-13 | D02978 | X1 | | | TB0037Z | 18 | BJ | | 115-199 |
| 0158 | 24 | GK | | | 3-0 | 21-51-13 | D02978 | X2 | | | D41845J | 17 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286N1024 | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | | |
| 0159 | 22 | | GA | | 3-0 | 21-51-13 | D02948 | | A3 | | D02980 | | A2 | | 115-199 |
| 0160 | 24 | | GK | | 2-0 | 21-51-13 | D02980 | | A1 | | TB0037Z | 17 | BJ | | 115-199 |
| 0161 | 24 | | GK | | 2-0 | 21-51-13 | D02980 | | X1 | | TB0037Z | 18 | BJ | | 115-199 |
| 0162 | 24 | | GK | | 3-0 | 21-51-13 | D02980 | | X2 | | D41845J | 18 | | | 115-199 |
| 0163 | 24 | | GK | | 3-0 | 21-51-13 | D41845J | | 12 | | TB0037Y | C013 | BJ | | 115-199 |
| 0164 | 24 | | GK | | 3-0 | 21-51-13 | D02948 | | X2 | | TB0037Y | C013 | BJ | | 115-199 |
| 0165 | 22 | | GA | | 3-0 | 21-51-13 | D02950 | | C2 | | D41845J | 37 | | | 115-199 |
| 0166 | 22 | | GA | | 3-0 | 21-51-13 | D02950 | | B2 | | D41845J | 38 | | | 115-199 |
| 0167 | 22 | | GA | | 3-0 | 21-51-13 | D02950 | | A2 | | D41845J | 39 | | | 115-199 |
| 0168 | 24 | | GK | | 3-0 | 21-51-13 | D02950 | | X2 | | TB0037Y | C013 | BJ | | 115-199 |
| 0169 | 22 | | GA | | 3-0 | 21-51-13 | D02948 | | C2 | | D41845J | 40 | | | 115-199 |
| 0170 | 22 | | GA | | 3-0 | 21-51-13 | D02948 | | B2 | | D41845J | 3 | | | 115-199 |
| 0171 | 22 | | GA | | 3-0 | 21-51-13 | D02948 | | A2 | | D41845J | 4 | | | 115-199 |
| 0172 | 24 | | GK | | 3-0 | 21-51-14 | D04138 | | 3 | | D41845J | 5 | | | 115-199 |
| 0173 | 24 | | GK | | 2-0 | 21-51-14 | D04138 | | 7 | | TB0037Z | 18 | BJ | | 115-199 |
| 0174 | 24 | | GK | | 3-0 | 21-51-13 | D02948 | | D2 | | TB0037Z | 18 | BJ | | 115-199 |
| 0175 | 24 | | GK | | 3-0 | 21-51-15 | D04052 | | 7 | | D41845J | 27 | | | 115-199 |
| 0176 | 24 | | GK | | 3-0 | 21-51-15 | D04052 | | 8 | | D41845J | 28 | | | 115-199 |
| 0177 | 24 | | GK | | 3-0 | 21-51-15 | D04052 | | 11 | | D41845J | 29 | | | 115-199 |
| 0178 | 24 | | GK | | 3-0 | 21-51-15 | D04052 | | 10 | | D41845J | 31 | | | 115-199 |
| 0180 | 24 | | GK | | 2-10 | 24-33-12 | TB0037Y | | C003 | BJ | D04774 | B2 | | | 001-099 |
| 0181 | 24 | | GK | | 3-0 | 21-51-22 | D41855J | | 45 | | TB0037Y | A015 | BJ | | 115-199 |
| 0182 | 24 | | GK | | 3-0 | 21-51-22 | D03008 | | X1 | | TB0037Y | A015 | BJ | | 115-199 |
| 0183 | 24 | | GK | | 3-0 | 21-51-22 | D03008 | | C1 | | D41855J | 6 | | | 115-199 |
| 0184 | 24 | | GK | | 3-0 | 21-51-22 | D03008 | | B1 | | D41855J | 5 | | | 115-199 |
| 0185 | 24 | | GK | | 3-0 | 21-51-22 | D03008 | | A1 | | D41855J | 4 | | | 115-199 |
| 0186 | 24 | | GK | | 3-0 | 21-51-22 | D03006 | | X1 | | TB0037Y | A015 | BJ | | 115-199 |
| 0187 | 24 | | GK | | 3-0 | 21-51-22 | D03006 | | C1 | | D41855J | 3 | | | 115-199 |
| 0188 | 24 | | GK | | 3-0 | 21-51-22 | D03006 | | B1 | | D41855J | 2 | | | 115-199 |
| 0189 | 24 | | GK | | 3-0 | 21-51-22 | D03006 | | A1 | | D41855J | 1 | | | 115-199 |
| 0190 | 24 | | GK | | 2-0 | 21-51-22 | D04096 | | 6 | | TB0037Y | A015 | BJ | | 115-199 |
| 0191 | 24 | | GK | | 3-0 | 21-51-22 | D04096 | | 1 | | D41855J | 7 | | | 115-199 |
| 0192 | 24 | | GK | | 2-0 | 21-51-22 | D04096 | | 13 | | GD01880 | DC.. | 2 | | 115-199 |
| 0193 | 24 | | GK | | 2-0 | 21-51-22 | D04096 | | 12 | | TB0037Y | C015 | BJ | | 115-199 |
| 0194 | 24 | | GK | | 1-11 | 24-32-41 | D04832 | | 7 | | D04834 | X1 | | * | 001-099 |
| 0195 | 24 | | GK | | 3-0 | 21-51-23 | D03008 | | D2 | | TB0037Z | 19 | BJ | | 115-199 |
| 0196 | 22 | | GA | | 3-0 | 21-51-23 | D03008 | | C3 | | D03032 | A2 | | | 115-199 |
| 0197 | 24 | | GK | | 2-0 | 21-51-23 | D03032 | | A1 | | TB0037Z | 19 | BJ | | 115-199 |
| 0198 | 24 | | GK | | 2-0 | 21-51-23 | D03032 | | X1 | | TB0037Z | 20 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | | | | | | | | | | | | | | | |
| | | 286N1024 | | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | |
| 0199 | 24 | GK | | | 3-0 | 21-51-23 | D03032 | | X2 | | D41855J | 17 | | | 115-199 |
| 0200 | 24 | GK | | | 3-0 | 21-51-23 | D03008 | | D3 | | D42216J | 8 | | | 115-199 |
| 0201 | 24 | GK | | | 2-0 | 21-51-23 | D03034 | | A1 | | TB0037Z | 19 | BJ | | 115-199 |
| 0202 | 24 | GK | | | 2-0 | 21-51-23 | D03034 | | X1 | | TB0037Z | 20 | BJ | | 115-199 |
| 0203 | 24 | GK | | | 3-0 | 21-51-23 | D03034 | | X2 | | D41855J | 39 | | | 115-199 |
| 0204 | 22 | GA | | | 3-0 | 21-51-23 | D03008 | | B3 | | D03034 | A2 | | | 115-199 |
| 0205 | 24 | GK | | | 2-0 | 21-51-23 | D03036 | | A1 | | TB0037Z | 19 | BJ | | 115-199 |
| 0206 | 24 | GK | | | 2-0 | 21-51-23 | D03036 | | X1 | | TB0037Z | 20 | BJ | | 115-199 |
| 0207 | 24 | GK | | | 3-0 | 21-51-23 | D03036 | | X2 | | D41855J | 40 | | | 115-199 |
| 0208 | 22 | GA | | | 3-0 | 21-51-23 | D03008 | | A3 | | D03036 | A2 | | | 115-199 |
| 0209 | 24 | GK | | | 2-9 | 24-32-41 | D40170J | | 2 | | D04834 | X1 | | * | 001-099 |
| 0209 | 20 | GA | | | 3-0 | 33-37-21 | D02287 | | C1 | | TB0037Y | C024 | BJ | | 115-199 |
| 0210 | 24 | GK | | | 3-0 | 21-51-23 | D03006 | | D3 | | D42238J | 15 | | | 115-199 |
| 0211 | 24 | GK | | | 3-0 | 21-51-23 | D03006 | | D2 | | TB0037Z | 20 | BJ | | 115-199 |
| 0212 | 22 | GA | | | 3-0 | 21-51-23 | D03006 | | C3 | | D03038 | A2 | | | 115-199 |
| 0214 | 24 | GK | | | 2-0 | 21-51-23 | D03038 | | A1 | | TB0037Z | 19 | BJ | | 115-199 |
| 0215 | 24 | GK | | | 2-0 | 21-51-23 | D03038 | | X1 | | TB0037Z | 20 | BJ | | 115-199 |
| 0216 | 24 | GK | | | 3-0 | 21-51-23 | D03038 | | X2 | | D41855J | 41 | | | 115-199 |
| 0217 | 22 | GA | | | 3-0 | 21-51-23 | D03006 | | B3 | | D03040 | A2 | | | 115-199 |
| 0218 | 24 | GK | | | 2-0 | 21-51-23 | D03040 | | A1 | | TB0037Z | 19 | BJ | | 115-199 |
| 0219 | 24 | GK | | | 2-0 | 21-51-23 | D03040 | | X1 | | TB0037Z | 20 | BJ | | 115-199 |
| 0220 | 24 | GK | | | 3-0 | 21-51-23 | D03040 | | X2 | | D41855J | 42 | | | 115-199 |
| 0221 | 24 | GK | | | 2-0 | 21-51-23 | D03042 | | A1 | | TB0037Z | 19 | BJ | | 115-199 |
| 0222 | 24 | GK | | | 2-0 | 21-51-23 | D03042 | | X1 | | TB0037Z | 20 | BJ | | 115-199 |
| 0223 | 24 | GK | | | 3-0 | 21-51-23 | D03042 | | X2 | | D41855J | 43 | | | 115-199 |
| 0224 | 22 | GA | | | 3-0 | 21-51-23 | D03006 | | A3 | | D03042 | A2 | | | 115-199 |
| 0225 | 24 | GK | | | 3-0 | 21-51-23 | D41855J | | 16 | | TB0037Y | C015 | BJ | | 115-199 |
| 0226 | 24 | GK | | | 3-0 | 21-51-23 | D03006 | | X2 | | TB0037Y | C015 | BJ | | 115-199 |
| 0227 | 24 | GK | | | 3-0 | 21-51-23 | D03008 | | X2 | | TB0037Y | C015 | BJ | | 115-199 |
| 0228 | 22 | GA | | | 3-0 | 21-51-23 | D03008 | | C2 | | D41855J | 32 | | | 115-199 |
| 0229 | 22 | GA | | | 3-0 | 21-51-23 | D03008 | | B2 | | D41855J | 33 | | | 115-199 |
| 0230 | 22 | GA | | | 3-0 | 21-51-23 | D03008 | | A2 | | D41855J | 34 | | | 115-199 |
| 0231 | 22 | GA | | | 3-0 | 21-51-23 | D03006 | | C2 | | D41855J | 35 | | | 115-199 |
| 0232 | 22 | GA | | | 3-0 | 21-51-23 | D03006 | | B2 | | D41855J | 36 | | | 115-199 |
| 0233 | 22 | GA | | | 3-0 | 21-51-23 | D03006 | | A2 | | D41855J | 37 | | | 115-199 |
| 0234 | 24 | GK | | | 3-0 | 21-51-24 | D41855J | | 29 | | TB0037Z | 19 | BJ | | 115-199 |
| 0235 | 24 | GK | | | 2-0 | 21-51-24 | D04060 | | 7 | | TB0037Z | 20 | BJ | | 115-199 |
| 0236 | 24 | GK | | | 3-0 | 21-51-24 | D04060 | | 3 | | D41855J | 28 | | | 115-199 |
| 0237 | 24 | GK | | | 3-0 | 21-51-25 | D04096 | | 7 | | D41855J | 21 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286N1024 | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | | |
| 0238 | 24 | | GK | | 3-0 | 21-51-25 | D04096 | | 8 | | D41855J | 22 | | | 115-199 |
| 0239 | 24 | | GK | | 3-0 | 21-51-25 | D04096 | | 11 | | D41855J | 24 | | | 115-199 |
| 0240 | 24 | | GK | | 3-0 | 21-51-25 | D04096 | | 10 | | D41855J | 26 | | | 115-199 |
| 0241 | 24 | | GK | | 2-1 | 24-33-12 | D42238J | | 4 | | D42178J | 14 | | | 001-099 |
| 0242 | 22 | | GA | | 2-4 | 49-61-11 | D41680J | | 19 | | D02434 | X2 | | | 001-099 |
| 0245 | 22 | | GA | | 1-3 | 49-61-11 | TB0037Y | A016 | BJ | | TB0037Z | 27 | BJ | | 001-099 |
| 0246 | 18 | | GA | | 1-5 | 24-31-41 | D01886 | | A2 | | D40170J | 4 | | | 001-099 |
| 0246 | 18 | | GA | | 3-0 | 24-31-41 | D01886 | | A2 | | D40170J | 4 | | | 115-199 |
| 0247 | 18 | | GA | | 1-5 | 24-31-41 | D01886 | | B2 | | D40170J | 5 | | | 001-099 |
| 0247 | 18 | | GA | | 3-0 | 24-31-41 | D01886 | | B2 | | D40170J | 5 | | | 115-199 |
| 0248 | 18 | | GA | | 1-5 | 24-31-41 | D01886 | | C2 | | D40170J | 6 | | | 001-099 |
| 0248 | 18 | | GA | | 3-0 | 24-31-41 | D01886 | | C2 | | D40170J | 6 | | | 115-199 |
| 0249 | 24 | | GK | | 3-0 | 24-31-41 | D01886 | | X2 | | TB0037B | A031 | 2 | | ALL |
| 0250 | 24 | | GK | | 1-10 | 24-31-41 | D01886 | | X1 | | D42050J | 7 | | | 001-099 |
| 0250 | 24 | | GK | | 3-0 | 24-31-41 | D01886 | | X1 | | D42050J | 7 | | | 115-199 |
| 0251 | 18 | | GA | | 1-10 | 24-31-41 | D01886 | | C3 | | D42050J | 10 | | | 001-099 |
| 0251 | 18 | | GA | | 3-0 | 24-31-41 | D01886 | | C3 | | D42050J | 10 | | | 115-199 |
| 0252 | 18 | | GA | | 1-10 | 24-31-41 | D01886 | | B3 | | D42050J | 2 | | | 001-099 |
| 0252 | 18 | | GA | | 3-0 | 24-31-41 | D01886 | | B3 | | D42050J | 2 | | | 115-199 |
| 0253 | 18 | | GA | | 1-10 | 24-31-41 | D01886 | | A3 | | D42050J | 4 | | | 001-099 |
| 0253 | 18 | | GA | | 3-0 | 24-31-41 | D01886 | | A3 | | D42050J | 4 | | | 115-199 |
| 0255 | 22 | | GA | | 3-3 | 24-32-41 | GD01880 | DC.. | 2 | | K10010 | X2 | C | | 001-099 |
| 0255 | 22 | | GA | | 3-0 | 24-32-41 | K10010 | X2 | C | | GD01880 | DC.. | 2 | | 115-199 |
| 0256 | 22 | | GA | | 1-9 | 49-41-11 | D41680J | | 38 | | TB0037Y | C009 | BJ | | 001-099 |
| 0256 | 22 | | GA | | 3-0 | 49-41-11 | D41680J | | 38 | | TB0037Y | C009 | BJ | | 115-199 |
| 0257 | 18 | | GA | | 3-0 | 33-37-21 | D02287 | | C2 | | D41932J | 4 | | | 115-199 |
| 0258 | 22 | | GA | | 2-9 | 49-72-11 | D42050J | | 19 | | TB0037Y | C009 | BJ | | 001-099 |
| 0258 | 22 | | GA | | 3-0 | 49-72-11 | D42050J | | 19 | | TB0037Y | C009 | BJ | | 115-199 |
| 0259 | 24 | | GK | | 3-0 | 36-11-41 | D02436 | | B1 | | D41680J | 1 | | | 115-199 |
| 0260 | 20 | | GA | | 3-0 | 36-11-41 | D41680J | | 2 | | D41688J | 3 | | | 001-099 |
| 0260 | 20 | | GA | | 2-0 | 36-11-41 | D41680J | | 2 | | D41688J | 3 | | | 115-199 |
| 0261 | 20 | | GA | | 3-0 | 36-11-41 | D41680J | | 3 | | D41688J | 5 | | | 001-099 |
| 0261 | 20 | | GA | | 2-0 | 36-11-41 | D41680J | | 3 | | D41688J | 5 | | | 115-199 |
| 0262 | 20 | | GA | | 3-0 | 36-11-41 | D41680J | | 4 | | D41688J | 7 | | | 001-099 |
| 0262 | 20 | | GA | | 2-0 | 36-11-41 | D41680J | | 4 | | D41688J | 7 | | | 115-199 |
| 0263 | 20 | | GA | | 3-0 | 36-11-41 | D41680J | | 5 | | D41688J | 9 | | | 001-099 |
| 0263 | 20 | | GA | | 2-0 | 36-11-41 | D41680J | | 5 | | D41688J | 9 | | | 115-199 |
| 0264 | 22 | | GA | | 2-2 | 52-35-11 | D04812 | | X2 | | TB0037Y | A023 | BJ | | 001-099 |
| 0264 | 22 | | GA | | 3-0 | 25-51-21 | D02287 | | B2 | | D42038J | 10 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 11

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286N1024 | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | | |
| 0294 | 22 | | GA | | 1-11 | 33-37-21 | D02287 | | X1 | | D42038J | 7 | | | 001-099 |
| 0294 | 22 | | GA | | 3-0 | 33-37-21 | D02287 | | X1 | | TB0037Y | A024 | BJ | | 115-199 |
| 0295 | 22 | | GA | | 2-4 | 33-37-21 | D02287 | | X2 | | TB0037Y | A023 | BJ | | 001-099 |
| 0295 | 22 | | GA | | 3-0 | 33-37-21 | D02287 | | X2 | | TB0037Y | A023 | BJ | | 115-199 |
| 0296 | 12 | | GA | | 1-11 | 33-37-21 | D41932J | | 14 | | T10002 | LV | E | | 001-099 |
| 0296 | 12 | | GA | | 3-5 | 33-37-21 | D42032J | | 4 | | T10002 | LV | E | | 115-199 |
| 0297 | 22 | | GA | | 2-8 | 52-35-11 | D42038J | | 4 | | TB0037Y | A023 | BJ | | 001-099 |
| 0297 | 22 | | GA | | 3-0 | 52-35-11 | D41855J | | 13 | | TB0037Y | A023 | BJ | | 115-199 |
| 0298 | 16 | | GA | | 1-9 | 52-35-11 | D42038J | | 20 | | D04812 | A2 | | | 001-099 |
| 0298 | 16 | | GA | | 3-0 | 52-35-11 | D42038J | | 20 | | K00036 | A2 | D | | 115-199 |
| 0299 | 16 | | GA | | 1-9 | 52-35-11 | D42038J | | 22 | | D04812 | B2 | | | 001-099 |
| 0299 | 16 | | GA | | 3-0 | 52-35-11 | D42038J | | 22 | | K00036 | B2 | D | | 115-199 |
| 0300 | 16 | | GA | | 1-9 | 52-35-11 | D42038J | | 24 | | D04812 | C2 | | | 001-099 |
| 0300 | 16 | | GA | | 3-0 | 52-35-11 | D42038J | | 24 | | K00036 | C2 | D | | 115-199 |
| 0301 | 22 | | GA | | 1-9 | 52-35-11 | D42038J | | 3 | | D04810 | X2 | | | 001-099 |
| 0301 | 22 | | GA | | 3-0 | 52-35-11 | D41855J | | 27 | | K00036 | Y1 | C | | 115-199 |
| 0302 | 22 | | GA | | 3-0 | 52-35-11 | K00036 | | X2 | C | TB0037Y | A023 | BJ | | 115-199 |
| 0303 | 22 | | GA | | 1-8 | 52-35-11 | D41932J | | 1 | | D04810 | X1 | | | 001-099 |
| 0303 | 22 | | GA | | 3-0 | 52-35-11 | D41932J | | 7 | | K00036 | Y2 | C | | 115-199 |
| 0304 | 16 | | GA | | 3-3 | 52-35-11 | D41932J | | 18 | | TB0037G | 2 | 2 | | 001-099 |
| 0304 | 16 | | GA | | 3-0 | 52-35-11 | D41932J | | 2 | | K00036 | A3 | D | * | 115-199 |
| 0305 | 16 | | GA | | 1-0 | 52-35-11 | K00036 | | A1 | D | K00036 | A3 | D | * | 115-199 |
| 0307 | 16 | | GA | | 2-0 | 52-35-11 | K00036 | | B3 | D | K00036 | C1 | D | * | 115-199 |
| 0308 | 16 | | GA | | 3-0 | 52-35-11 | D41932J | | 22 | | TB0037G | 21 | 2 | | 001-099 |
| 0308 | 16 | | GA | | 3-0 | 52-35-11 | D41932J | | 8 | | K00036 | C1 | D | * | 115-199 |
| 0309 | 16 | | GA | | 2-0 | 52-35-11 | K00036 | | C3 | D | K00036 | B1 | D | * | 115-199 |
| 0310 | 22 | | GA | | 2-1 | 52-35-11 | D41932J | | 2 | | D04812 | X1 | | | 001-099 |
| 0310 | 22 | | GA | | 3-0 | 52-35-11 | D41932J | | 9 | | K00036 | X1 | C | | 115-199 |
| 0311 | 16 | | GA | | 3-0 | 52-35-11 | D41932J | | 20 | | TB0037G | 22 | 2 | | 001-099 |
| 0311 | 16 | | GA | | 3-0 | 52-35-11 | D41932J | | 10 | | K00036 | B1 | D | * | 115-199 |
| 0312 | 16 | | GA | | 2-4 | 49-61-11 | D42050J | | 1 | | R00012 | C | E | * | 001-099 |
| 0312 | 16 | | GA | | 3-0 | 49-61-11 | D42050J | | 1 | | R00012 | C | E | * | 115-199 |
| 0313 | 24 | | GK | | 2-2 | 24-33-12 | D05025 | | B2 | | TB0037Y | C003 | BJ | | 001-099 |
| 0314 | 20 | | GA | | 1-10 | 24-33-12 | D05025 | | B1 | | GD01880 | DC.. | 2 | | 001-099 |
| 0325 | 24 | | GK | | 2-8 | 49-61-14 | D41688J | | 4 | | D02380 | A3 | | | 001-099 |
| 0325 | 24 | | GK | | 3-0 | 49-61-14 | D41688J | | 4 | | D02380 | A3 | | | 115-199 |
| 0326 | 24 | | GK | | 2-8 | 49-61-14 | D41688J | | 6 | | D02380 | A1 | | | 001-099 |
| 0326 | 24 | | GK | | 3-0 | 49-61-14 | D41688J | | 6 | | D02380 | A1 | | | 115-199 |
| 0330 | 24 | | GK | | 3-0 | 21-51-13 | D42238J | | 11 | | TB0037Y | A014 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286N1024 | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | | |
| 0331 | 24 | | GK | | 3-0 | 21-51-13 | D41845J | 34 | | | TB0037Y | A014 | BJ | | 115-199 |
| 0342 | 22 | | GA | | 1-8 | 49-61-11 | D41680J | 49 | | | TB0037Y | A016 | BJ | | 001-099 |
| 0396 | 24 | | GK | | 2-3 | 24-32-41 | D04832 | 6 | | | TB0037Y | A036 | BJ | | 001-099 |
| 0396 | 24 | | GK | | 2-0 | 24-32-41 | D04832 | 6 | | | TB0037Y | A036 | BJ | | 115-199 |
| 0397 | 24 | | GK | | 2-3 | 24-32-41 | D04832 | 1 | | | TB0037B | A035 | 2 | | 001-099 |
| 0397 | 24 | | GK | | 2-0 | 24-32-41 | D04832 | 1 | | | TB0037B | A035 | 2 | | 115-199 |
| 0398 | 24 | | GK | | 2-3 | 24-32-41 | D04832 | 3 | | | TB0037Y | A036 | BJ | | 001-099 |
| 0398 | 24 | | GK | | 2-0 | 24-32-41 | D04832 | 3 | | | TB0037Y | A036 | BJ | | 115-199 |
| 0399 | 24 | | GK | | 2-10 | 24-32-41 | D03084 | B1 | | * | TB0037B | C035 | 2 | | 001-099 |
| 0399 | 24 | | GK | | 2-0 | 24-32-41 | D03084 | B1 | | * | TB0037B | C035 | 2 | | 115-199 |
| 0403 | 24 | | GK | | 2-0 | 24-33-12 | D41680J | 16 | | | D07678 | A2 | | | 002-008, 010-099 |
| 0404 | 24 | | GK | | 1-10 | 24-33-12 | D07678 | A3 | | | GD01880 | DC.. | 2 | | 002-008, 010-099 |
| 0405 | 24 | | GK | | 2-2 | 24-33-12 | D07678 | X1 | | | TB0037Y | C029 | BJ | | 002-008, 010-099 |
| 0419 | 22 | | GA | | 1-9 | 49-61-11 | D41680J | 40 | | | TB0037Y | A011 | BJ | | 001-099 |
| 0419 | 22 | | GA | | 3-0 | 49-61-11 | D41680J | 40 | | | TB0037Y | A011 | BJ | | 115-199 |
| 0420 | 22 | | GA | | 1-9 | 49-61-11 | D41680J | 52 | | | TB0037Y | A011 | BJ | | 001-099 |
| 0420 | 22 | | GA | | 3-0 | 49-61-11 | D41680J | 52 | | | TB0037Y | A011 | BJ | | 115-199 |
| 0421 | 22 | | GA | | 1-9 | 49-61-11 | D41680J | 43 | | | TB0037Y | A011 | BJ | | 001-099 |
| 0421 | 22 | | GA | | 3-0 | 49-61-11 | D41680J | 43 | | | TB0037Y | A011 | BJ | | 115-199 |
| 0422 | 22 | | GA | | 1-11 | 49-61-11 | D02410 | 8 | | | GD01880 | DC.. | 2 | | 001-099 |
| 0422 | 22 | | GA | | 2-0 | 49-61-11 | D02410 | 8 | | | GD01880 | DC.. | 2 | | 115-199 |
| 0423 | 22 | | GA | | 2-2 | 49-61-11 | D02410 | 6 | | | D41680J | 42 | | | 001-099 |
| 0423 | 22 | | GA | | 3-0 | 49-61-11 | D02410 | 6 | | | D41680J | 42 | | | 115-199 |
| 0424 | 22 | | GA | | 1-11 | 49-61-11 | D02410 | 4 | | | GD01880 | DC.. | 2 | | 001-099 |
| 0424 | 22 | | GA | | 2-0 | 49-61-11 | D02410 | 4 | | | GD01880 | DC.. | 2 | | 115-199 |
| 0425 | 22 | | GA | | 2-2 | 49-61-11 | D02410 | 2 | | | D41680J | 50 | | | 001-099 |
| 0425 | 22 | | GA | | 3-0 | 49-61-11 | D02410 | 2 | | | D41680J | 50 | | | 115-199 |
| 0426 | 22 | | GA | | 2-3 | 49-61-11 | D02410 | 5 | | | TB0037Y | A003 | BJ | | 001-099 |
| 0426 | 22 | | GA | | 2-0 | 49-61-11 | D02410 | 5 | | | TB0037Y | A003 | BJ | | 115-199 |
| 0450 | 24 | | GK | | 2-3 | 24-31-41 | D02416 | B3 | | | D03084 | B1 | | * | 001-099 |
| 0450 | 24 | | GK | | 3-0 | 24-31-41 | D02416 | B3 | | | D03084 | B1 | | * | 115-199 |
| 0451 | 24 | | GK | | 2-8 | 24-33-12 | D41680J | 54 | | | D04774 | B3 | | | 001-099 |
| 0452 | 20 | | GA | | 3-0 | 25-51-21 | D02612 | B3 | | | D41932J | 16 | | | 115-199 |
| 1004 | 24 | | G1 | AM | 1-4 | 28-25-21 | D41062J | 1 | | | D02378 | B2 | | | 001-099 |
| 1004 | 24 | | G1 | AM | 3-0 | 28-25-21 | D41062J | 1 | | | D02378 | B2 | | | 115-199 |
| 1004Z | | | | AM | 0-0 | 28-25-21 | D41062J | DED | | | D02378 | DED | | | ALL |
| 2004B | 24 | | GL | AG | 2-10 | 24-34-11 | D41680J | 32 | | | D42050J | 9 | | | 001-099 |
| 2004B | 22 | | GB | AG | 4-0 | 24-34-11 | D41680J | 32 | | | D42050J | 9 | | | 115-199 |
| 2004R | 24 | | GL | AG | 0-0 | 24-34-11 | D41680J | 33 | | | D42050J | 17 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1024 | 286N1024 | | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | |
| 2004R | 22 | GB | AG | | 0-0 | 24-34-11 | D41680J | 33 | | | D42050J | 17 | | | 115-199 |
| 2005B | 24 | GL | BA | | 3-0 | 21-51-12 | D41845J | 11 | | | SM00001 | | WI | | 115-199 |
| 2005R | 24 | GL | BA | | 0-0 | 21-51-12 | D41845J | 10 | | | D04052 | 5 | | | 115-199 |
| 2006B | 24 | GL | BB | | 3-0 | 21-51-12 | D41845J | 33 | | | SM00001 | | WI | | 115-199 |
| 2006R | 24 | GL | BB | | 0-0 | 21-51-12 | D41845J | 32 | | | D04052 | 4 | | | 115-199 |
| 2007B | 24 | GL | BC | | 3-0 | 21-51-14 | D41845J | 21 | | | D04138 | 8 | | | 115-199 |
| 2007R | 24 | GL | BC | | 0-0 | 21-51-14 | D41845J | 22 | | | D04138 | 4 | | | 115-199 |
| 2008B | 24 | GL | BD | | 3-0 | 21-51-14 | D41845J | 2 | | | D04138 | 5 | | | 115-199 |
| 2008R | 24 | GL | BD | | 0-0 | 21-51-14 | D41845J | 1 | | | D04138 | 1 | | | 115-199 |
| 2009B | 24 | GL | BE | | 3-0 | 21-51-14 | D41845J | 26 | | | D04138 | 2 | | | 115-199 |
| 2009R | 24 | GL | BE | | 0-0 | 21-51-14 | D41845J | 25 | | | D04138 | 6 | | | 115-199 |
| 2010B | 24 | GL | BF | | 3-0 | 21-51-22 | D41855J | 12 | | | SM00002 | | WI | | 115-199 |
| 2010R | 24 | GL | BF | | 0-0 | 21-51-22 | D41855J | 11 | | | D04096 | 5 | | | 115-199 |
| 2011B | 24 | GL | BG | | 3-0 | 21-51-22 | D41855J | 9 | | | SM00002 | | WI | | 115-199 |
| 2011R | 24 | GL | BG | | 0-0 | 21-51-22 | D41855J | 10 | | | D04096 | 4 | | | 115-199 |
| 2012B | 24 | GL | BH | | 3-0 | 21-51-24 | D41855J | 14 | | | D04060 | 8 | | | 115-199 |
| 2012R | 24 | GL | BH | | 0-0 | 21-51-24 | D41855J | 15 | | | D04060 | 4 | | | 115-199 |
| 2013B | 24 | GL | BI | | 3-0 | 21-51-24 | D41855J | 31 | | | D04060 | 5 | | | 115-199 |
| 2013R | 24 | GL | BI | | 0-0 | 21-51-24 | D41855J | 30 | | | D04060 | 1 | | | 115-199 |
| 2014B | 24 | GL | BJ | | 3-0 | 21-51-24 | D41855J | 20 | | | D04060 | 2 | | | 115-199 |
| 2014R | 24 | GL | BJ | | 0-0 | 21-51-24 | D41855J | 19 | | | D04060 | 6 | | | 115-199 |
| 2501B | 24 | G2 | DA | | 1-8 | 23-41-12 | D41680J | 34 | | | TB0037Y | A025 | BJ | | 001-099 |
| 2501R | 24 | G2 | DA | | 0-0 | 23-41-12 | D41680J | 35 | | | TB0037Y | C026 | BJ | | 001-099 |
| 2501Z | | | DA | | 0-0 | 23-41-12 | D41680J | 37 | | | TB0037Y | A026 | BJ | | 001-099 |
| 2502B | 24 | G2 | DB | | 2-11 | 23-41-12 | D41688J | 12 | | | TB0037Y | A025 | BJ | | 001-099 |
| 2502R | 24 | G2 | DB | | 0-0 | 23-41-12 | D41688J | 11 | | | TB0037Y | C026 | BJ | | 001-099 |
| 2502Z | | | DB | | 0-0 | 23-41-12 | D41688J | 8 | | | TB0037Y | A026 | BJ | | 001-099 |
| 2503B | 24 | G2 | DC | | 2-8 | 23-41-12 | D42050J | 11 | | | TB0037Y | A025 | BJ | | 001-099 |
| 2503R | 24 | G2 | DC | | 0-0 | 23-41-12 | D42050J | 12 | | | TB0037Y | C026 | BJ | | 001-099 |
| 2503Z | | | DC | | 0-0 | 23-41-12 | D42050J | 14 | | | TB0037Y | A026 | BJ | | 001-099 |
| 3501B | 24 | G3 | DA | | 3-0 | 23-41-12 | D41680J | 34 | | | TB0037Y | A025 | BJ | | 115-199 |
| 3501R | 24 | G3 | DA | | 0-0 | 23-41-12 | D41680J | 35 | | | TB0037Y | C026 | BJ | | 115-199 |
| 3501Y | 24 | G3 | DA | | 0-0 | 23-41-12 | D41680J | 36 | | | TB0037Y | C025 | BJ | | 115-199 |
| 3501Z | | | DA | | 0-0 | 23-41-12 | D41680J | 37 | | | TB0037Y | A026 | BJ | | 115-199 |
| 3502B | 24 | G3 | DB | | 3-0 | 23-41-12 | D41688J | 17 | | | TB0037Y | A025 | BJ | | 115-199 |
| 3502R | 24 | G3 | DB | | 0-0 | 23-41-12 | D41688J | 18 | | | TB0037Y | C026 | BJ | | 115-199 |
| 3502Y | 24 | G3 | DB | | 0-0 | 23-41-12 | D41688J | 19 | | | TB0037Y | C025 | BJ | | 115-199 |
| 3502Z | | | DB | | 0-0 | 23-41-12 | D41688J | 20 | | | TB0037Y | A026 | BJ | | 115-199 |
| 3503B | 24 | G3 | DC | | 3-0 | 23-41-12 | D42050J | 11 | | | TB0037Y | A025 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1024 | 286N1024 | | | E6 RELAY PANEL HARNESS (continued) | | | | | | | | | | |
| 3503R | 24 | G3 | DC | 0-0 | 23-41-12 | D42050J | 12 | | | TB0037Y | C026 | BJ | | 115-199 |
| 3503Y | 24 | G3 | DC | 0-0 | 23-41-12 | D42050J | 13 | | | TB0037Y | C025 | BJ | | 115-199 |
| 3503Z | | | DC | 0-0 | 23-41-12 | D42050J | 14 | | | TB0037Y | A026 | BJ | | 115-199 |
| PA01 | | | | 0-0 | 24-32-41 | D04834 | G2 | | | D04834 | G3 | | | 115-199 |
| PB01 | | | | 0-0 | 24-32-41 | D04834 | G2 | | | D04834 | G3 | | | 001-099 |
| W1026 | 286N1026 | | | E6 INTEGRATION - APU CB PANEL | | | | | | | | | | |
| 0001 | *1 | CQ | | 4-4 | 24-31-41 | TB5047 | 1 | H | | C00868 | =L | F | | 001-099 |
| 0001 | *1 | CQ | | 1-1 | 24-31-41 | TB5047 | 1 | H | | C00868 | =L | F | | 115-199 |
| 0002 | 08 | HA | | 3-0 | 24-31-41 | M00207 | + | H | | C00868 | =B | F | * | 001-099 |
| 0002 | 08 | HA | | 1-5 | 24-31-41 | M00207 | + | H | | C00868 | =B | F | * | 115-199 |
| 0003 | 16 | GA | | 2-0 | 24-31-41 | C00869 | =L | D | | C00821 | =B | D | | 115-199 |
| 0005 | 08 | HA | | 1-2 | 24-31-41 | C00869 | =B | D | | C00868 | =B | F | * | 001-099 |
| 0005 | 08 | HA | | 0-5 | 24-31-41 | C00869 | =B | D | | C00868 | =B | F | * | 115-199 |
| 0007 | 16 | GA | | 1-0 | 24-31-41 | C01382 | =B | D | | C01385 | =B | D | * | 115-199 |
| 0008 | 16 | GA | | 2-0 | 24-31-41 | C00820 | =B | D | | C01385 | =B | D | * | 115-199 |
| 0010 | 16 | GA | | 9-4 | 49-61-11 | C00020 | =B | D | | D42050P | 1 | | | 001-099 |
| 0010 | 16 | GA | | 11-0 | 49-61-11 | C00020 | =B | D | | D42050P | 1 | | | 115-199 |
| 0016 | 18 | GA | | 9-3 | 49-61-14 | C01385 | =L | D | | D42050P | 6 | | | 001-099 |
| 0016 | 18 | GA | | 11-0 | 49-61-14 | C01385 | =L | D | | D42050P | 6 | | | 115-199 |
| 0020 | 22 | GA | | 9-0 | 24-31-41 | C00820 | =L | D | | D42050P | 7 | | | 001-099 |
| 0020 | 22 | GA | | 11-0 | 24-31-41 | C00820 | =L | D | | D42050P | 7 | | | 115-199 |
| 0021 | 22 | GA | | 9-1 | 24-33-12 | D04766 | 11 | | | D42178P | 1 | | | 001-099 |
| 0022 | 20 | GA | | 2-3 | 24-33-12 | D04766 | 9 | | | GD03095 | DC.. | E | | 001-099 |
| 0023 | 20 | GA | | 2-5 | 24-33-12 | D04766 | 2 | | | GD03091 | ST.. | E | | 001-099 |
| 0024 | 22 | GA | | 9-1 | 24-33-12 | D04766 | 4 | | | D42178P | 4 | | | 001-099 |
| 0025 | 22 | GA | | 9-1 | 24-33-12 | D04766 | 7 | | | D42178P | 5 | | | 001-099 |
| 0026 | 20 | GA | | 2-6 | 24-33-12 | M10496 | 5A | 1A | | GD03091 | ST.. | E | | 001-099 |
| 0027 | 22 | GA | | 9-2 | 24-33-12 | M10496 | S3 | 1A | | D42178P | 7 | | | 001-099 |
| 0028 | 22 | GA | | 9-2 | 24-33-12 | M10496 | 3 | 1A | | D42178P | 8 | | | 001-099 |
| 0029 | 22 | GA | | 9-2 | 24-33-12 | M10496 | S1 | 1A | | D42178P | 9 | | | 001-099 |
| 0030 | 22 | GA | | 9-2 | 24-33-12 | M10496 | 4 | 1A | | D42178P | 10 | | | 001-099 |
| 0031 | 22 | GA | | 9-3 | 24-33-12 | D01888 | 9 | | | D42178P | 11 | | | 001-099 |
| 0032 | 22 | GA | | 9-3 | 24-33-12 | D01888 | 8 | | | D42178P | 12 | | | 001-099 |
| 0033 | 22 | GA | | 8-11 | 24-33-12 | C04286 | =L | D | | D42050P | 15 | | | 001-099 |
| 0041 | 24 | GK | | 9-2 | 24-33-12 | M10496 | S2 | 1A | | D42178P | 14 | | | 001-099 |
| 0046 | 22 | GA | | 1-5 | 49-72-11 | C04246 | =L | D | | N10017 | + | D | | 001-099 |
| 0046 | 22 | GA | | 7-0 | 49-72-11 | C04246 | =L | D | | N10017 | + | D | | 115-199 |
| 0047 | 22 | GA | | 2-2 | 49-72-11 | C00020 | =L | D | | N10032 | + | \$ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1026 | 286N1026 | | | E6 INTEGRATION - APU CB PANEL (continued) | | | | | | | | | | | |
| 0047 | 22 | | GA | | 7-0 | 49-72-11 | C00020 | =L | D | * | N10032 | + | \$ | | 115-199 |
| 0048 | 22 | | GA | | 9-1 | 49-72-11 | N10017 | - | D | | D42050P | 18 | | | 001-099 |
| 0048 | 22 | | GA | | 13-0 | 49-72-11 | N10017 | - | D | | D42050P | 18 | | | 115-199 |
| 0049 | 22 | | GA | | 9-9 | 49-72-11 | N10032 | - | \$ | | D42050P | 19 | | | 001-099 |
| 0049 | 22 | | GA | | 13-0 | 49-72-11 | N10032 | - | \$ | | D42050P | 19 | | | 115-199 |
| 0050 | 16 | | GA | | 9-1 | 49-61-11 | C01382 | =L | D | | D42050P | 8 | | | 001-099 |
| 0050 | 16 | | GA | | 11-0 | 49-61-11 | C01382 | =L | D | | D42050P | 8 | | | 115-199 |
| 0051 | 20 | | GA | | 9-2 | 49-61-11 | C00020 | =L | D | | D42050P | 16 | | | 001-099 |
| 0051 | 20 | | GA | | 11-0 | 49-61-11 | C00020 | =L | D | * | D42050P | 16 | | | 115-199 |
| 0083 | 24 | | GK | | 9-2 | 24-34-11 | C00821 | =L | D | | D42050P | 3 | | | 001-099 |
| 0083 | 22 | | GA | | 11-0 | 24-34-11 | C00821 | =L | D | | D42050P | 3 | | | 115-199 |
| 0084 | 20 | | GA | | 3-0 | 24-32-41 | D42050P | 24 | | | D01076 | G | | | 001-099 |
| 0084 | 20 | | GA | | 7-0 | 24-32-41 | D42050P | 24 | | | D01076 | G | | | 115-199 |
| 0085 | 20 | | GA | | 3-0 | 24-32-41 | D42050P | 23 | | | D01076 | C | | | 001-099 |
| 0085 | 20 | | GA | | 7-0 | 24-32-41 | D42050P | 23 | | | D01076 | C | | | 115-199 |
| 0086 | 20 | | GA | | 3-0 | 24-32-41 | D42050P | 22 | | | D01076 | B | | | 001-099 |
| 0086 | 20 | | GA | | 7-0 | 24-32-41 | D42050P | 22 | | | D01076 | B | | | 115-199 |
| 0087 | 20 | | GA | | 3-0 | 24-32-41 | D42050P | 21 | | | D01076 | A | | | 001-099 |
| 0087 | 20 | | GA | | 7-0 | 24-32-41 | D42050P | 21 | | | D01076 | A | | | 115-199 |
| 0088 | 20 | | GA | | 8-10 | 24-32-41 | D42050P | 27 | | | C00089 | A2 | D | | 001-099 |
| 0088 | 20 | | GA | | 11-0 | 24-32-41 | D42050P | 27 | | | C00089 | A2 | D | | 115-199 |
| 0089 | 20 | | GA | | 8-10 | 24-32-41 | D42050P | 28 | | | C00089 | B2 | D | | 001-099 |
| 0089 | 20 | | GA | | 11-0 | 24-32-41 | D42050P | 28 | | | C00089 | B2 | D | | 115-199 |
| 0090 | 20 | | GA | | 8-11 | 24-32-41 | D42050P | 25 | | | C00089 | C2 | D | | 001-099 |
| 0090 | 20 | | GA | | 11-0 | 24-32-41 | D42050P | 25 | | | C00089 | C2 | D | | 115-199 |
| 0091 | 10 | | HA | | 9-0 | 24-32-41 | C00089 | A1 | D | | K10010 | A1 | E | | 001-099 |
| 0091 | 10 | | HA | | 8-4 | 24-32-41 | C00089 | A1 | D | | K10010 | A1 | E | | 115-199 |
| 0092 | 10 | | HA | | 8-11 | 24-32-41 | C00089 | B1 | D | | K10010 | B1 | E | | 001-099 |
| 0092 | 10 | | HA | | 9-0 | 24-32-41 | C00089 | B1 | D | | K10010 | B1 | E | | 115-199 |
| 0093 | 10 | | HA | | 8-10 | 24-32-41 | C00089 | C1 | D | | K10010 | C1 | E | | 001-099 |
| 0093 | 10 | | HA | | 8-4 | 24-32-41 | C00089 | C1 | D | | K10010 | C1 | E | | 115-199 |
| 0094 | 20 | | GA | | 3-0 | 24-32-41 | D42050P | 20 | | | D01076 | I | | | 001-099 |
| 0094 | 20 | | GA | | 7-0 | 24-32-41 | D42050P | 20 | | | D01076 | I | | | 115-199 |
| 0100 | 22 | | GA | | 4-2 | 24-31-41 | D01888 | | | FA | GD03091 | ST.. | E | | 010-099 |
| 0101 | 22 | | GA | | 3-0 | 24-31-41 | D01890 | | | FB | GD03095 | DC.. | E | | 010-099 |
| 0106 | 18 | | GA | | 8-10 | 24-31-41 | D42050P | 10 | | | D01888 | 10 | | | 001-099 |
| 0106 | 18 | | GA | | 11-0 | 24-31-41 | D42050P | 10 | | | D01888 | 10 | | | 115-199 |
| 0107 | 18 | | GA | | 8-10 | 24-31-41 | D42050P | 2 | | | D01888 | 7 | | | 001-099 |
| 0107 | 18 | | GA | | 11-0 | 24-31-41 | D42050P | 2 | | | D01888 | 7 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|---|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1026 | 286N1026 | | | E6 INTEGRATION - APU CB PANEL (continued) | | | | | | | | | | | | |
| 0108 | 18 | GA | | | 8-10 | 24-31-41 | D42050P | | 4 | | | D01888 | | 4 | | 001-099 |
| 0108 | 18 | GA | | | 11-0 | 24-31-41 | D42050P | | 4 | | | D01888 | | 4 | | 115-199 |
| 0109 | 24 | GK | | | 0-7 | 24-31-41 | D01888 | | 5 | | | D01888 | | 6 | | 001-099 |
| 0109 | 24 | GK | | | 1-0 | 24-31-41 | D01888 | | 5 | | | D01888 | | 6 | | 115-199 |
| 0110 | 24 | GK | | | 6-4 | 24-31-41 | D01888 | | 1 | | | D01890 | | 1 | | 001-099 |
| 0110 | 24 | GK | | | 5-0 | 24-31-41 | D01888 | | 1 | | | D01890 | | 1 | | 115-199 |
| 0111 | 24 | GK | | | 6-4 | 24-31-41 | D01888 | | 3 | | | D01890 | | 3 | | 001-099 |
| 0111 | 24 | GK | | | 5-0 | 24-31-41 | D01888 | | 3 | | | D01890 | | 3 | | 115-199 |
| 0112 | 24 | GK | | | 6-4 | 24-31-41 | D01888 | | 11 | | | D01890 | | 11 | | 001-009 |
| 0112 | 24 | GK | | | 5-0 | 24-31-41 | D01888 | | 11 | | | D01890 | | 11 | | 115-199 |
| 0113 | 24 | GK | | | 6-4 | 24-31-41 | D01888 | | 12 | | | D01890 | | 12 | | 001-009 |
| 0113 | 24 | GK | | | 5-0 | 24-31-41 | D01888 | | 12 | | | D01890 | | 12 | | 115-199 |
| 0114 | 20 | GA | | | 4-2 | 24-31-41 | D01888 | | 2 | | | GD03091 | ST.. | E | | 001-099 |
| 0114 | 20 | GA | | | 6-0 | 24-31-41 | D01888 | | 2 | | | GD00740 | ST.. | E | | 115-199 |
| 0115 | 24 | GK | | | 9-4 | 24-31-41 | D01890 | | 8 | | | D42050P | | 26 | | 001-099 |
| 0115 | 24 | GK | | | 11-0 | 24-31-41 | D01890 | | 8 | | | D42050P | | 26 | | 115-199 |
| 0116 | 20 | GA | | | 3-0 | 24-31-41 | D01890 | | 9 | | | GD03095 | DC.. | E | | 001-099 |
| 0116 | 20 | GA | | | 8-0 | 24-31-41 | D01890 | | 9 | | | GD00744 | DC.. | E | | 115-199 |
| 0117 | 10 | HA | | | 4-10 | 24-32-41 | D01076 | | D | | | K10010 | A2 | E | | 001-099 |
| 0117 | 10 | HA | | | 5-0 | 24-32-41 | D01076 | | D | | | K10010 | A2 | E | | 115-199 |
| 0118 | 10 | HA | | | 4-9 | 24-32-41 | D01076 | | E | | | K10010 | B2 | E | | 001-099 |
| 0118 | 10 | HA | | | 5-0 | 24-32-41 | D01076 | | E | | | K10010 | B2 | E | | 115-199 |
| 0119 | 10 | HA | | | 4-9 | 24-32-41 | D01076 | | F | | | K10010 | C2 | E | | 001-099 |
| 0119 | 10 | HA | | | 5-0 | 24-32-41 | D01076 | | F | | | K10010 | C2 | E | | 115-199 |
| 0120 | 20 | GA | | | 6-2 | 24-32-41 | D01076 | | H | | | GD03368 | DC.. | E | | 001-099 |
| 0120 | 20 | GA | | | 6-0 | 24-32-41 | D01076 | | H | | | GD02610 | DC.. | 2 | | 115-199 |
| 0121 | 20 | GA | | | 4-7 | 24-31-41 | D01888 | | 8 | | | GD03095 | DC.. | E | | 115-199 |
| 2004B | 24 | GL | AC | | 9-10 | 24-34-11 | M10251 | =D | D | | | D42050P | | 9 | | 001-099 |
| 2004B | 22 | GB | AC | | 11-0 | 24-34-11 | M10251 | =D | D | | | D42050P | | 9 | | 115-199 |
| 2004R | 24 | GL | AC | | 0-0 | 24-34-11 | M10251 | =C | D | | | D42050P | | 17 | | 001-099 |
| 2004R | 22 | GB | AC | | 0-0 | 24-34-11 | M10251 | =C | D | | | D42050P | | 17 | | 115-199 |
| 2501B | 24 | G2 | AA | | 9-2 | 23-41-12 | SM00218 | | 9 | | | D42050P | | 11 | | 001-099 |
| 2501R | 24 | G2 | AA | | 0-0 | 23-41-12 | SM00220 | | 9 | | | D42050P | | 12 | | 001-099 |
| 2501Z | | | AA | | 0-0 | 23-41-12 | SM00222 | | 9 | | | D42050P | | 14 | | 001-099 |
| 2502B | 24 | G2 | DC | | 6-4 | 24-31-41 | D01888 | | 11 | | | D01890 | | 11 | | 010-099 |
| 2502R | 24 | G2 | DC | | 0-0 | 24-31-41 | D01888 | | 12 | | | D01890 | | 12 | | 010-099 |
| 2502Z | | | DC | | 0-0 | 24-31-41 | D01888 | | | | FA | D01890 | | | FB | 010-099 |
| 3503B | 24 | G3 | AA | | 12-0 | 23-41-12 | SM00218 | | WI | | | D42050P | | 11 | | 115-199 |
| 3503R | 24 | G3 | AA | | 0-0 | 23-41-12 | SM00220 | | WI | | | D42050P | | 12 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1026 | 286N1026 | | | E6 INTEGRATION - APU CB PANEL (continued) | | | | | | | | | | | |
| 3503Y | 24 | G3 | | AA | 0-0 | 23-41-12 | SM00222 | | WI | | D42050P | 13 | | | 115-199 |
| 3503Z | | | | AA | 0-0 | 23-41-12 | SM00222 | DED | | | D42050P | 14 | | | 115-199 |
| A-BL | | | | AB | 0-0 | 23-41-12 | D00415 | BLU | | | SM00218 | | 9 | | 001-099 |
| A-BL | | | | AB | 0-0 | 23-41-12 | D00415 | BLU | | | SM00218 | | WI | | 115-199 |
| A-RD | | | | AB | 0-0 | 23-41-12 | D00415 | RED | | | SM00220 | | 9 | | 001-099 |
| A-RD | | | | AB | 0-0 | 23-41-12 | D00415 | RED | | | SM00220 | | WI | | 115-199 |
| A-YE | | | | AB | 0-0 | 23-41-12 | D00415 | BLK | | | SM00222 | | 9 | | 001-099 |
| A-YE | | | | AB | 0-0 | 23-41-12 | D00415 | BLK | | | SM00222 | | WI | | 115-199 |
| ZZAA | 02 | ZB | | | 0-0 | 24-31-41 | C01382 | =B | D | | C04246 | =B | D | | 115-199 |
| ZZAB | 03 | ZB | | | 0-0 | 24-31-41 | C00820 | =B | D | | C04286 | =B | D | | 001-099 |
| ZZAC | 02 | ZB | | | 0-0 | 24-31-41 | C04246 | =B | D | | C01382 | =B | D | | 001-099 |
| ZZOA | 00 | ZB | | | 0-0 | 24-31-41 | C00821 | =B | D | | C04286 | =B | D | | 001-099 |
| ZZOB | 00 | ZB | | | 0-0 | 24-31-41 | C00820 | =B | D | | C00821 | =B | D | | 001-099 |
| ZZOB | 02 | ZB | | | 0-0 | 24-31-41 | C00821 | =B | D | | C00820 | =B | D | | 115-199 |
| ZZXA | 02 | ZA | | | 0-0 | 24-31-41 | C00821 | =B | D | | C04246 | =B | D | | 001-099 |
| ZZXB | 02 | ZA | | | 0-0 | 24-31-41 | C01382 | =B | D | | C01385 | =B | D | | 001-099 |
| ZZXC | 02 | ZA | | | 0-0 | 24-31-41 | C00869 | =L | D | | C00820 | =B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1020

Page 19 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1030 | | 286N1030 | | | | E6-2 SHELF | | | | | | | | | |
| 0001 | 20 | GA | | | 3-0 | 21-51-12 | D02964C | | 2 | | D42182J | | 1 | | 115-199 |
| 0002 | 20 | GA | | | 3-0 | 21-51-12 | D02964C | | 4 | | GD02014 | AC.. | 2 | | 115-199 |
| 0003 | 24 | GK | | | 3-0 | 21-51-12 | D02964C | | 3 | | GD02014 | ST.. | 2 | | 115-199 |
| 0007 | 24 | GK | | | 3-0 | 21-51-12 | D02964B | | C13 | | D42182J | | 3 | | 115-199 |
| 0008 | 24 | GK | | | 3-0 | 21-51-12 | D02964B | | C15 | | D42182J | | 4 | | 115-199 |
| 0009 | 24 | GK | | | 3-0 | 21-51-12 | D02964B | | B13 | | D42182J | | 5 | | 115-199 |
| 0010 | 24 | GK | | | 3-0 | 21-51-12 | D02964B | | B15 | | D42182J | | 6 | | 115-199 |
| 0011 | 24 | GK | | | 3-0 | 21-51-12 | D02964B | | A13 | | D42182J | | 7 | | 115-199 |
| 0012 | 24 | GK | | | 3-0 | 21-51-12 | D02964B | | A15 | | D42182J | | 8 | | 115-199 |
| 0013 | 24 | GK | | | 3-0 | 21-51-12 | D02964B | | D07 | | D42182J | | 9 | | 115-199 |
| 0020 | 24 | GK | | | 3-0 | 21-51-15 | D42182J | | 53 | | D02964B | C05 | | | 115-199 |
| 0024 | 24 | GK | | | 3-0 | 21-51-12 | D02964A | | C15 | | GD02014 | DC.. | 2 | | 115-199 |
| 0025 | 24 | GK | | | 3-0 | 21-51-15 | D02964B | | C07 | | D42182J | | 42 | | 115-199 |
| 0026 | 24 | GK | | | 3-0 | 21-51-15 | D02964B | | B09 | | D42182J | | 43 | | 115-199 |
| 0027 | 24 | GK | | | 3-0 | 21-51-24 | D04130B | | A15 | | D42186J | | 1 | | 115-199 |
| 0028 | 24 | GK | | | 2-0 | 21-51-24 | D04130B | | C15 | | GD02014 | AC.. | 2 | | 115-199 |
| 0029 | 24 | GK | | | 2-0 | 21-51-24 | D04130B | | B14 | | GD02014 | DC.. | 2 | | 115-199 |
| 0030 | 24 | GK | | | 3-0 | 21-61-11 | D02558B | | A09 | | D42186J | | 11 | | 115-199 |
| 0031 | 24 | GK | | | 3-0 | 21-61-11 | D02558B | | A15 | | D42186J | | 12 | | 115-199 |
| 0032 | 24 | GK | | | 3-0 | 21-61-11 | D02558B | | A13 | | D42186J | | 13 | | 115-199 |
| 0033 | 24 | GK | | | 3-0 | 21-61-11 | D02558B | | A12 | | D42186J | | 14 | | 115-199 |
| 0034 | 24 | GK | | | 3-0 | 21-61-11 | D02558B | | A11 | | D42186J | | 15 | | 115-199 |
| 0038 | 24 | GK | | | 3-0 | 21-61-21 | D02558B | | B09 | | D42186J | | 26 | | 115-199 |
| 0039 | 24 | GK | | | 3-0 | 21-61-21 | D02558B | | B15 | | D42186J | | 27 | | 115-199 |
| 0040 | 24 | GK | | | 3-0 | 21-61-21 | D02558B | | B13 | | D42186J | | 28 | | 115-199 |
| 0041 | 24 | GK | | | 3-0 | 21-61-21 | D02558B | | B12 | | D42186J | | 29 | | 115-199 |
| 0042 | 24 | GK | | | 3-0 | 21-61-21 | D02558B | | B11 | | D42186J | | 30 | | 115-199 |
| 0050 | 24 | GK | | | 3-0 | 21-61-31 | D02558B | | C11 | | D42186J | | 42 | | 115-199 |
| 0051 | 24 | GK | | | 3-0 | 21-61-31 | D02558B | | C09 | | D42186J | | 43 | | 115-199 |
| 0052 | 24 | GK | | | 3-0 | 21-61-31 | D02558B | | C12 | | D42186J | | 44 | | 115-199 |
| 0053 | 24 | GK | | | 3-0 | 21-61-31 | D02558B | | C13 | | D42186J | | 45 | | 115-199 |
| 0054 | 24 | GK | | | 3-0 | 21-61-31 | D02558B | | C15 | | D42186J | | 46 | | 115-199 |
| 0055 | 24 | GK | | | 3-0 | 21-61-51 | D02558C | | 4 | | GD02017 | AC.. | 2 | | 115-199 |
| 0056 | 24 | GK | | | 3-0 | 21-61-51 | D02558C | | 2 | | D42182J | | 52 | | 115-199 |
| 0057 | 24 | GK | | | 3-0 | 21-61-51 | D02558B | | C03 | | D42188J | | 3 | | 115-199 |
| 0058 | 24 | GK | | | 3-0 | 21-61-51 | D02558A | | C15 | | GD02017 | DC.. | 2 | | 115-199 |
| 0059 | 24 | GK | | | 3-0 | 21-51-14 | D04130A | | C15 | | GD02014 | AC.. | 2 | | 115-199 |
| 0060 | 24 | GK | | | 3-0 | 21-51-14 | D04130A | | B14 | | GD02014 | DC.. | 2 | | 115-199 |
| 0061 | 24 | GK | | | 3-0 | 21-51-14 | D04130C | | 3 | | GD02014 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1030 | 286N1030 | | | | E6-2 SHELF (continued) | | | | | | | | | | | | |
| 0062 | 24 | | GK | | 3-0 | 21-61-51 | D02558C | | 3 | | | GD02017 | ST.. | 2 | | 115-199 | |
| 0171 | 24 | | GK | | 3-0 | 21-51-14 | D04130A | | A15 | | | D42182J | 12 | | | 115-199 | |
| 0346 | 22 | | GK | | 3-0 | 21-51-22 | D03026C | | 2 | | | D42196J | 48 | | | 115-199 | |
| 0347 | 20 | | GA | | 3-0 | 21-51-22 | D03026C | | 4 | | | GD02017 | AC.. | 2 | | 115-199 | |
| 0348 | 24 | | GK | | 3-0 | 21-51-22 | D03026C | | 3 | | | GD02017 | ST.. | 2 | | 115-199 | |
| 0350 | 24 | | GK | | 3-0 | 21-51-22 | D03026B | | C13 | | | D42196J | 6 | | | 115-199 | |
| 0351 | 24 | | GK | | 3-0 | 21-51-22 | D03026B | | C15 | | | D42196J | 5 | | | 115-199 | |
| 0352 | 24 | | GK | | 3-0 | 21-51-22 | D03026B | | B13 | | | D42196J | 4 | | | 115-199 | |
| 0353 | 24 | | GK | | 3-0 | 21-51-22 | D03026B | | B15 | | | D42196J | 3 | | | 115-199 | |
| 0354 | 24 | | GK | | 3-0 | 21-51-22 | D03026B | | A13 | | | D42196J | 2 | | | 115-199 | |
| 0355 | 24 | | GK | | 3-0 | 21-51-22 | D03026B | | A15 | | | D42196J | 1 | | | 115-199 | |
| 0356 | 24 | | GK | | 3-0 | 21-51-22 | D03026B | | D07 | | | D42196J | 7 | | | 115-199 | |
| 0360 | 24 | | GK | | 3-0 | 21-51-25 | D42196J | | 35 | | | D03026B | C05 | | | 115-199 | |
| 0367 | 24 | | GK | | 3-0 | 21-51-22 | D03026A | | C15 | | | GD02017 | DC.. | 2 | | 115-199 | |
| 0368 | 24 | | GK | | 3-0 | 21-51-25 | D03026B | | C07 | | | D42196J | 36 | | | 115-199 | |
| 0369 | 24 | | GK | | 3-0 | 21-51-25 | D03026B | | B09 | | | D42196J | 37 | | | 115-199 | |
| 2001B | 24 | | GL | DA | 3-0 | 21-51-12 | D02964B | | B02 | | | D42182J | 11 | | | 115-199 | |
| 2001R | 24 | | GL | DA | 0-0 | 21-51-12 | D02964B | | B01 | | | D42182J | 10 | | | 115-199 | |
| 2002B | 24 | | GL | AG | 3-0 | 21-51-14 | D02964B | | C01 | | | D42182J | 40 | | | 115-199 | |
| 2002R | 24 | | GL | AG | 0-0 | 21-51-14 | D02964B | | C02 | | | D42182J | 41 | | | 115-199 | |
| 2003B | 24 | | GL | AH | 3-0 | 21-51-15 | D02964A | | D04 | | | D42182J | 44 | | | 115-199 | |
| 2003R | 24 | | GL | AH | 0-0 | 21-51-15 | D02964A | | D05 | | | D42182J | 45 | | | 115-199 | |
| 2004B | 24 | | GL | AI | 3-0 | 21-51-24 | D04130B | | B12 | | | D42186J | 3 | | | 115-199 | |
| 2004R | 24 | | GL | AI | 0-0 | 21-51-24 | D04130B | | A12 | | | D42186J | 2 | | | 115-199 | |
| 2005B | 24 | | GL | AJ | 3-0 | 21-51-24 | D04130B | | B09 | | | D42186J | 5 | | | 115-199 | |
| 2005R | 24 | | GL | AJ | 0-0 | 21-51-24 | D04130B | | A09 | | | D42186J | 4 | | | 115-199 | |
| 2006B | 24 | | GL | AK | 3-0 | 21-51-24 | D04130B | | B10 | | | D42186J | 7 | | | 115-199 | |
| 2006R | 24 | | GL | AK | 0-0 | 21-51-24 | D04130B | | A10 | | | D42186J | 6 | | | 115-199 | |
| 2007B | 24 | | GL | AM | 3-0 | 21-61-11 | D02558A | | A07 | | | D42186J | 20 | | | 115-199 | |
| 2007R | 24 | | GL | AM | 0-0 | 21-61-11 | D02558A | | A06 | | | D42186J | 19 | | | 115-199 | |
| 2008B | 24 | | GL | AN | 3-0 | 21-61-11 | D02558A | | A05 | | | D42186J | 22 | | | 115-199 | |
| 2008R | 24 | | GL | AN | 0-0 | 21-61-11 | D02558A | | A04 | | | D42186J | 21 | | | 115-199 | |
| 2009B | 24 | | GL | AP | 3-0 | 21-61-21 | D02558A | | B07 | | | D42186J | 35 | | | 115-199 | |
| 2009R | 24 | | GL | AP | 0-0 | 21-61-21 | D02558A | | B06 | | | D42186J | 34 | | | 115-199 | |
| 2010B | 24 | | GL | AQ | 3-0 | 21-61-21 | D02558A | | B05 | | | D42188J | 22 | | | 115-199 | |
| 2010R | 24 | | GL | AQ | 0-0 | 21-61-21 | D02558A | | B04 | | | D42188J | 21 | | | 115-199 | |
| 2011B | 24 | | GL | AS | 3-0 | 21-61-31 | D02558A | | C07 | | | D42186J | 51 | | | 115-199 | |
| 2011R | 24 | | GL | AS | 0-0 | 21-61-31 | D02558A | | C06 | | | D42186J | 50 | | | 115-199 | |
| 2012B | 24 | | GL | AT | 3-0 | 21-61-31 | D02558A | | C05 | | | D42186J | 53 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 2

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------|-------------|----|-------|------------------------|-------|----------|---------|------|------|--------|---------|------|------|---------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1030 | 286N1030 | | | E6-2 SHELF (continued) | | | | | | | | | | | |
| 2012R | 24 | GL | AT | | 0-0 | 21-61-31 | D02558A | | C04 | | D42186J | 52 | | 115-199 | |
| 2013B | 24 | GL | AV | | 3-0 | 21-61-51 | D02558B | | D03 | | D42188J | 2 | | 115-199 | |
| 2013R | 24 | GL | AV | | 0-0 | 21-61-51 | D02558B | | D04 | | D42188J | 1 | | 115-199 | |
| 2014B | 24 | GL | AW | | 3-0 | 21-61-51 | D02558B | | B05 | | D03026B | A05 | | 115-199 | |
| 2014R | 24 | GL | AW | | 0-0 | 21-61-51 | D02558B | | B06 | | D03026B | A06 | | 115-199 | |
| 2015B | 24 | GL | AX | | 3-0 | 21-61-51 | D02558B | | B04 | | D03026B | A04 | | 115-199 | |
| 2015R | 24 | GL | AX | | 0-0 | 21-61-51 | D02558B | | B03 | | D03026B | A03 | | 115-199 | |
| 2016B | 24 | GL | AY | | 3-0 | 21-61-51 | D02558B | | B02 | | D03026B | A02 | | 115-199 | |
| 2016R | 24 | GL | AY | | 0-0 | 21-61-51 | D02558B | | B01 | | D03026B | A01 | | 115-199 | |
| 2017B | 24 | GL | AZ | | 3-0 | 21-61-51 | D02558B | | B08 | | D03026B | A08 | | 115-199 | |
| 2017R | 24 | GL | AZ | | 0-0 | 21-61-51 | D02558B | | B07 | | D03026B | A07 | | 115-199 | |
| 2018B | 24 | GL | BA | | 3-0 | 21-61-51 | D02558B | | D08 | | D03026B | B08 | | 115-199 | |
| 2018R | 24 | GL | BA | | 0-0 | 21-61-51 | D02558B | | D07 | | D03026B | B07 | | 115-199 | |
| 2019B | 24 | GL | BB | | 3-0 | 21-61-51 | D02558B | | C01 | | D42188J | 5 | | 115-199 | |
| 2019R | 24 | GL | BB | | 0-0 | 21-61-51 | D02558B | | C02 | | D42188J | 4 | | 115-199 | |
| 2020B | 24 | GL | BC | | 3-0 | 21-61-51 | D02964B | | A06 | | D02558B | A06 | | 115-199 | |
| 2020R | 24 | GL | BC | | 0-0 | 21-61-51 | D02964B | | A05 | | D02558B | A05 | | 115-199 | |
| 2021B | 24 | GL | BD | | 3-0 | 21-61-51 | D02964B | | A08 | | D02558B | A08 | | 115-199 | |
| 2021R | 24 | GL | BD | | 0-0 | 21-61-51 | D02964B | | A07 | | D02558B | A07 | | 115-199 | |
| 2022B | 24 | GL | BE | | 3-0 | 21-61-51 | D02964B | | B08 | | D02558B | C08 | | 115-199 | |
| 2022R | 24 | GL | BE | | 0-0 | 21-61-51 | D02964B | | B07 | | D02558B | C07 | | 115-199 | |
| 2023B | 24 | GL | BF | | 3-0 | 21-61-51 | D02964B | | A04 | | D02558B | A04 | | 115-199 | |
| 2023R | 24 | GL | BF | | 0-0 | 21-61-51 | D02964B | | A03 | | D02558B | A03 | | 115-199 | |
| 2024B | 24 | GL | BG | | 3-0 | 21-61-51 | D02964B | | A02 | | D02558B | A02 | | 115-199 | |
| 2024R | 24 | GL | BG | | 0-0 | 21-61-51 | D02964B | | A01 | | D02558B | A01 | | 115-199 | |
| 2025B | 24 | GL | BH | | 3-0 | 21-51-14 | D04130A | | B09 | | D42182J | 47 | | 115-199 | |
| 2025R | 24 | GL | BH | | 0-0 | 21-51-14 | D04130A | | A09 | | D42182J | 46 | | 115-199 | |
| 2026B | 24 | GL | BI | | 3-0 | 21-51-14 | D04130A | | B10 | | D42182J | 49 | | 115-199 | |
| 2026R | 24 | GL | BI | | 0-0 | 21-51-14 | D04130A | | A10 | | D42182J | 48 | | 115-199 | |
| 2027B | 24 | GL | BJ | | 3-0 | 21-51-14 | D04130A | | B12 | | D42182J | 51 | | 115-199 | |
| 2027R | 24 | GL | BJ | | 0-0 | 21-51-14 | D04130A | | A12 | | D42182J | 50 | | 115-199 | |
| 2029B | 24 | GL | BW | | 3-0 | 21-51-12 | D42182J | | 21 | | D02964A | A04 | | 115-199 | |
| 2029R | 24 | GL | BW | | 0-0 | 21-51-12 | D42182J | | 20 | | D02964A | A05 | | 115-199 | |
| 2030B | 24 | GL | BY | | 3-0 | 21-61-11 | D02964A | | C05 | | D42186J | 37 | | 115-199 | |
| 2030R | 24 | GL | BY | | 0-0 | 21-61-11 | D02964A | | C04 | | D42186J | 36 | | 115-199 | |
| 2031B | 24 | GL | BZ | | 4-0 | 21-51-12 | D02964B | | D01 | | D42196J | 54 | | 115-199 | |
| 2031R | 24 | GL | BZ | | 0-0 | 21-51-12 | D02964B | | D02 | | D42196J | 53 | | 115-199 | |
| 2032B | 24 | GL | CA | | 3-0 | 21-51-12 | D02964B | | D05 | | D42182J | 15 | | 115-199 | |
| 2032R | 24 | GL | CA | | 0-0 | 21-51-12 | D02964B | | D06 | | D42182J | 16 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 3

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1030 | 286N1030 | | | E6-2 SHELF (continued) | | | | | | | | | | | |
| 2033B | 24 | GL | CT | | 3-0 | 21-51-12 | D02964A | B04 | | | D42182J | 14 | | | 115-199 |
| 2033R | 24 | GL | CT | | 0-0 | 21-51-12 | D02964A | B05 | | | D42182J | 13 | | | 115-199 |
| 2103B | 24 | GL | CJ | | 3-0 | 21-51-22 | D03026B | B02 | | | D42196J | 11 | | | 115-199 |
| 2103R | 24 | GL | CJ | | 0-0 | 21-51-22 | D03026B | B01 | | | D42196J | 12 | | | 115-199 |
| 2104B | 24 | GL | CK | | 3-0 | 21-51-24 | D03026B | C01 | | | D42196J | 31 | | | 115-199 |
| 2104R | 24 | GL | CK | | 0-0 | 21-51-24 | D03026B | C02 | | | D42196J | 32 | | | 115-199 |
| 2105B | 24 | GL | CB | | 3-0 | 21-51-25 | D03026A | D04 | | | D42196J | 41 | | | 115-199 |
| 2105R | 24 | GL | CB | | 0-0 | 21-51-25 | D03026A | D05 | | | D42196J | 42 | | | 115-199 |
| 2108B | 24 | GL | CP | | 3-0 | 21-51-22 | D03026A | B04 | | | D42196J | 10 | | | 115-199 |
| 2108R | 24 | GL | CP | | 0-0 | 21-51-22 | D03026A | B05 | | | D42196J | 9 | | | 115-199 |
| 2109B | 24 | GL | CI | | 3-0 | 21-51-22 | D03026B | D05 | | | D42196J | 29 | | | 115-199 |
| 2109R | 24 | GL | CI | | 0-0 | 21-51-22 | D03026B | D06 | | | D42196J | 30 | | | 115-199 |
| 2110B | 24 | GL | CR | | 3-0 | 21-51-22 | D03026A | A05 | | | D42196J | 33 | | | 115-199 |
| 2110R | 24 | GL | CR | | 0-0 | 21-51-22 | D03026A | A04 | | | D42196J | 34 | | | 115-199 |
| 2112B | 24 | GL | CH | | 3-0 | 21-61-21 | D03026A | C05 | | | D42188J | 24 | | | 115-199 |
| 2112R | 24 | GL | CH | | 0-0 | 21-61-21 | D03026A | C04 | | | D42188J | 23 | | | 115-199 |
| 2113B | 24 | GL | CN | | 3-0 | 21-51-22 | D03026B | D01 | | | D42196J | 43 | | | 115-199 |
| 2113R | 24 | GL | CN | | 0-0 | 21-51-22 | D03026B | D02 | | | D42196J | 44 | | | 115-199 |
| 3001B | 24 | GM | AA | | 3-0 | 21-51-12 | D02964A | C11 | | | D42182J | 23 | | | 115-199 |
| 3001R | 24 | GM | AA | | 0-0 | 21-51-12 | D02964A | C10 | | | D42182J | 22 | | | 115-199 |
| 3001Y | 24 | GM | AA | | 0-0 | 21-51-12 | D02964A | C12 | | | D42182J | 24 | | | 115-199 |
| 3002B | 24 | GM | AB | | 3-0 | 21-51-12 | D02964A | C02 | | | D42182J | 26 | | | 115-199 |
| 3002R | 24 | GM | AB | | 0-0 | 21-51-12 | D02964A | C03 | | | D42182J | 25 | | | 115-199 |
| 3002Y | 24 | GM | AB | | 0-0 | 21-51-12 | D02964A | C01 | | | D42182J | 27 | | | 115-199 |
| 3003B | 24 | GM | AC | | 3-0 | 21-51-12 | D02964A | B11 | | | D42182J | 29 | | | 115-199 |
| 3003R | 24 | GM | AC | | 0-0 | 21-51-12 | D02964A | B10 | | | D42182J | 28 | | | 115-199 |
| 3003Y | 24 | GM | AC | | 0-0 | 21-51-12 | D02964A | B12 | | | D42182J | 30 | | | 115-199 |
| 3004B | 24 | GM | AD | | 3-0 | 21-51-12 | D02964A | B02 | | | D42182J | 32 | | | 115-199 |
| 3004R | 24 | GM | AD | | 0-0 | 21-51-12 | D02964A | B03 | | | D42182J | 31 | | | 115-199 |
| 3004Y | 24 | GM | AD | | 0-0 | 21-51-12 | D02964A | B01 | | | D42182J | 33 | | | 115-199 |
| 3005B | 24 | GM | AE | | 3-0 | 21-51-12 | D02964A | A11 | | | D42182J | 35 | | | 115-199 |
| 3005R | 24 | GM | AE | | 0-0 | 21-51-12 | D02964A | A10 | | | D42182J | 34 | | | 115-199 |
| 3005Y | 24 | GM | AE | | 0-0 | 21-51-12 | D02964A | A12 | | | D42182J | 36 | | | 115-199 |
| 3006B | 24 | GM | AF | | 3-0 | 21-51-12 | D02964A | A02 | | | D42182J | 38 | | | 115-199 |
| 3006R | 24 | GM | AF | | 0-0 | 21-51-12 | D02964A | A01 | | | D42182J | 37 | | | 115-199 |
| 3006Y | 24 | GM | AF | | 0-0 | 21-51-12 | D02964A | A03 | | | D42182J | 39 | | | 115-199 |
| 3007B | 24 | GM | AL | | 3-0 | 21-61-11 | D02558A | A02 | | | D42186J | 9 | | | 115-199 |
| 3007R | 24 | GM | AL | | 0-0 | 21-61-11 | D02558A | A01 | | | D42186J | 8 | | | 115-199 |
| 3007Y | 24 | GM | AL | | 0-0 | 21-61-11 | D02558A | A03 | | | D42186J | 10 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 4

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1030 | 286N1030 | | | E6-2 SHELF (continued) | | | | | | | | | | | |
| 3008B | 24 | | GM | AR | 3-0 | 21-61-21 | D02558A | B02 | | | D42186J | 24 | | | 115-199 |
| 3008R | 24 | | GM | AR | 0-0 | 21-61-21 | D02558A | B01 | | | D42186J | 23 | | | 115-199 |
| 3008Y | 24 | | GM | AR | 0-0 | 21-61-21 | D02558A | B03 | | | D42186J | 25 | | | 115-199 |
| 3009B | 24 | | GM | AU | 3-0 | 21-61-31 | D02558A | C02 | | | D42186J | 48 | | | 115-199 |
| 3009R | 24 | | GM | AU | 0-0 | 21-61-31 | D02558A | C01 | | | D42186J | 47 | | | 115-199 |
| 3009Y | 24 | | GM | AU | 0-0 | 21-61-31 | D02558A | C03 | | | D42186J | 49 | | | 115-199 |
| 3014B | 24 | | GM | CL | 3-0 | 21-51-22 | D03026A | A11 | | | D42190J | 29 | | | 115-199 |
| 3014R | 24 | | GM | CL | 0-0 | 21-51-22 | D03026A | A10 | | | D42190J | 28 | | | 115-199 |
| 3014Y | 24 | | GM | CL | 0-0 | 21-51-22 | D03026A | A12 | | | D42190J | 30 | | | 115-199 |
| 3015B | 24 | | GM | CM | 3-0 | 21-51-22 | D03026A | A02 | | | D42190J | 26 | | | 115-199 |
| 3015R | 24 | | GM | CM | 0-0 | 21-51-22 | D03026A | A01 | | | D42190J | 25 | | | 115-199 |
| 3015Y | 24 | | GM | CM | 0-0 | 21-51-22 | D03026A | A03 | | | D42190J | 27 | | | 115-199 |
| 3017B | 24 | | GM | BK | 3-0 | 21-61-31 | D02558A | C11 | | | D42186J | 40 | | | 115-199 |
| 3017R | 24 | | GM | BK | 0-0 | 21-61-31 | D02558A | C10 | | | D42186J | 41 | | | 115-199 |
| 3017Y | 24 | | GM | BK | 0-0 | 21-61-31 | D02558A | C12 | | | D42186J | 39 | | | 115-199 |
| 3018B | 24 | | GM | BT | 3-0 | 21-61-11 | D02558A | A11 | | | D42186J | 17 | | | 115-199 |
| 3018R | 24 | | GM | BT | 0-0 | 21-61-11 | D02558A | A10 | | | D42186J | 16 | | | 115-199 |
| 3018Y | 24 | | GM | BT | 0-0 | 21-61-11 | D02558A | A12 | | | D42186J | 18 | | | 115-199 |
| 3019B | 24 | | GM | BU | 3-0 | 21-51-12 | D42182J | 19 | | | D02964B | A09 | | | 115-199 |
| 3019R | 24 | | GM | BU | 0-0 | 21-51-12 | D42182J | 17 | | | D02964B | A10 | | | 115-199 |
| 3019Y | 24 | | GM | BU | 0-0 | 21-51-12 | D42182J | 18 | | | D02964B | A11 | | | 115-199 |
| 3020B | 24 | | GM | BX | 3-0 | 21-61-21 | D02558A | B11 | | | D42186J | 32 | | | 115-199 |
| 3020R | 24 | | GM | BX | 0-0 | 21-61-21 | D02558A | B10 | | | D42186J | 31 | | | 115-199 |
| 3020Y | 24 | | GM | BX | 0-0 | 21-61-21 | D02558A | B12 | | | D42186J | 33 | | | 115-199 |
| 3110B | 24 | | GM | CF | 3-0 | 21-51-22 | D03026A | C11 | | | D42190J | 14 | | | 115-199 |
| 3110R | 24 | | GM | CF | 0-0 | 21-51-22 | D03026A | C10 | | | D42190J | 13 | | | 115-199 |
| 3110Y | 24 | | GM | CF | 0-0 | 21-51-22 | D03026A | C12 | | | D42190J | 15 | | | 115-199 |
| 3111B | 24 | | GM | CE | 3-0 | 21-51-22 | D03026A | C02 | | | D42190J | 17 | | | 115-199 |
| 3111R | 24 | | GM | CE | 0-0 | 21-51-22 | D03026A | C03 | | | D42190J | 16 | | | 115-199 |
| 3111Y | 24 | | GM | CE | 0-0 | 21-51-22 | D03026A | C01 | | | D42190J | 18 | | | 115-199 |
| 3112B | 24 | | GM | CC | 3-0 | 21-51-22 | D03026A | B11 | | | D42190J | 19 | | | 115-199 |
| 3112R | 24 | | GM | CC | 0-0 | 21-51-22 | D03026A | B10 | | | D42190J | 20 | | | 115-199 |
| 3112Y | 24 | | GM | CC | 0-0 | 21-51-22 | D03026A | B12 | | | D42190J | 21 | | | 115-199 |
| 3113B | 24 | | GM | CD | 3-0 | 21-51-22 | D03026A | B02 | | | D42190J | 23 | | | 115-199 |
| 3113R | 24 | | GM | CD | 0-0 | 21-51-22 | D03026A | B03 | | | D42190J | 22 | | | 115-199 |
| 3113Y | 24 | | GM | CD | 0-0 | 21-51-22 | D03026A | B01 | | | D42190J | 24 | | | 115-199 |
| 3117B | 22 | | GC | CG | 3-0 | 21-51-22 | D03026B | A11 | | | D42196J | 46 | | | 115-199 |
| 3117R | 22 | | GC | CG | 0-0 | 21-51-22 | D03026B | A10 | | | D42196J | 45 | | | 115-199 |
| 3117Y | 22 | | GC | CG | 0-0 | 21-51-22 | D03026B | A09 | | | D42196J | 47 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 5

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1032 | 286N1032 | | | E6-4 SHELF HARNESS | | | | | | | | | | | |
| 0020 | 24 | | GK | | 3-0 | 49-61-11 | D01796B | | D10 | | GD02440 | DC.. | 2 | | 115-199 |
| 0036 | 24 | | GK | | 3-0 | 32-41-11 | D02744B | | D15 | | D42180J | 21 | | | 115-199 |
| 0037 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | D03 | | D42180J | 36 | | | 115-199 |
| 0038 | 22 | | GA | | 3-0 | 32-46-11 | D02794B | | D15 | | GD02440 | DC.. | 2 | | 115-199 |
| 0039 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | C07 | | D42180J | 20 | | | 115-199 |
| 0073 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | D05 | | D42208J | 6 | | | 115-199 |
| 0074 | 22 | | GA | | 3-0 | 32-46-11 | D02794B | | D14 | | GD02440 | DC.. | 2 | | 115-199 |
| 0075 | 22 | | GA | | 3-0 | 32-46-11 | D02794B | | C15 | | GD02441 | ST.. | 2 | | 115-199 |
| 0076 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | D12 | | D42180J | 1 | | | 115-199 |
| 0077 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | C10 | | D42180J | 2 | | | 115-199 |
| 0078 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | C11 | | D42180J | 3 | | | 115-199 |
| 0079 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | C12 | | D42180J | 4 | | | 115-199 |
| 0080 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | C13 | | D42180J | 5 | | | 115-199 |
| 0081 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | D10 | | D42180J | 6 | | | 115-199 |
| 0082 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | D11 | | D42180J | 7 | | | 115-199 |
| 0083 | 24 | | GK | | 3-0 | 32-46-11 | D02794B | | D09 | | D42180J | 8 | | | 115-199 |
| 0102 | 22 | | GA | | 3-0 | 29-33-11 | D42214J | | 6 | | D02598A | A08 | | | 115-199 |
| 0103 | 22 | | GA | | 3-0 | 29-33-11 | D02598B | | A11 | | D42214J | 7 | | | 115-199 |
| 0104 | 22 | | GA | | 3-0 | 29-33-11 | D02598B | | A01 | | D42214J | 8 | | | 115-199 |
| 0105 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | A14 | | D41686J | 7 | | | 115-199 |
| 0107 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | A05 | | D41686J | 8 | | | 115-199 |
| 0110 | 24 | | GK | | 3-0 | 29-33-11 | D02598B | | A08 | | D41686J | 9 | | | 115-199 |
| 0115 | 24 | | GK | | 4-0 | 29-33-11 | D02598B | | A09 | | D41662J | 24 | | | 115-199 |
| 0116 | 24 | | GK | | 4-0 | 29-33-11 | D02598A | | A15 | | D41686J | 17 | | | 115-199 |
| 0117 | 24 | | GK | | 4-0 | 29-33-11 | D02598A | | A06 | | D42218J | 7 | | | 115-199 |
| 0118 | 24 | | GK | | 3-0 | 29-33-11 | D02598B | | C07 | | D42028J | 1 | | | 115-199 |
| 0122 | 24 | | GK | | 3-0 | 29-33-11 | D02598B | | B07 | | D42028J | 5 | | | 115-199 |
| 0123 | 24 | | GK | | 3-0 | 29-33-11 | D02598B | | A07 | | D42028J | 6 | | | 115-199 |
| 0124 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | C13 | | D41686J | 1 | | | 115-199 |
| 0128 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | B13 | | D41686J | 5 | | | 115-199 |
| 0129 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | A13 | | D41686J | 6 | | | 115-199 |
| 0130 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | C04 | | D41686J | 25 | | | 115-199 |
| 0134 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | B04 | | D41686J | 26 | | | 115-199 |
| 0135 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | A04 | | D41686J | 27 | | | 115-199 |
| 0136 | 24 | | GK | | 3-0 | 29-33-11 | D02598B | | A14 | | D42028J | 7 | | | 115-199 |
| 0137 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | C05 | | D42028J | 8 | | | 115-199 |
| 0138 | 24 | | GK | | 3-0 | 29-33-11 | D02598A | | C14 | | D42028J | 9 | | | 115-199 |
| 0139 | 24 | | GK | | 3-0 | 29-33-11 | D02598B | | C08 | | D42028J | 10 | | | 115-199 |
| 0315 | 16 | | GA | | 5-0 | 49-61-11 | D01796C | | 9 | | D41662J | 15 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 6

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1032 | 286N1032 | | | E6-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0316 | 16 | GA | | | 3-0 | 49-61-11 | D01796C | 11 | | | GD02440 | DC.. | 2 | | 115-199 |
| 0317 | 16 | GA | | | 3-0 | 49-61-11 | D01796C | 2 | | | GD02441 | ST.. | 2 | | 115-199 |
| 0318 | 22 | GA | | | 5-0 | 49-61-11 | D01796B | K06 | | | D41662J | 4 | | | 115-199 |
| 0319 | 22 | GA | | | 5-0 | 49-61-11 | D01796B | B08 | | | D41662J | 13 | | | 115-199 |
| 0320 | 22 | GA | | | 5-0 | 49-61-11 | D01796B | A05 | | | D41662J | 7 | | | 115-199 |
| 0321 | 22 | GA | | | 5-0 | 49-61-11 | D01796B | H08 | | | D41662J | 5 | | | 115-199 |
| 0322 | 22 | GA | | | 5-0 | 49-61-11 | D01796B | H07 | | | D41662J | 6 | | | 115-199 |
| 0323 | 22 | GA | | | 5-0 | 49-61-11 | D41662J | 12 | | | D01796B | D06 | | | 115-199 |
| 0324 | 22 | GA | | | 3-0 | 49-72-11 | D01796B | G05 | | | TB0300Y | A004 | BJ | | 115-199 |
| 0328 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | J10 | | | D41676J | 1 | | | 115-199 |
| 0329 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | J07 | | | D41676J | 2 | | | 115-199 |
| 0330 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | J08 | | | D41676J | 3 | | | 115-199 |
| 0331 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | C05 | | | D41676J | 4 | | | 115-199 |
| 0332 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | D11 | | | D41676J | 5 | | | 115-199 |
| 0333 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | F06 | | | D41676J | 6 | | | 115-199 |
| 0334 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | F07 | | | D41676J | 7 | | | 115-199 |
| 0335 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | B10 | | | D41676J | 8 | | | 115-199 |
| 0336 | 22 | GA | | | 5-0 | SPARE | D01796B | CAP | Y | | D41676J | 9 | | | 115-199 |
| 0337 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | J04 | | | D41676J | 10 | | | 115-199 |
| 0338 | 22 | GA | | | 5-0 | 49-14-11 | D01796B | J05 | | | D41676J | 11 | | | 115-199 |
| 0339 | 22 | GA | | | 5-0 | 49-14-11 | D01796C | 4 | | | D41676J | 12 | | | 115-199 |
| 0340 | 22 | GA | | | 5-0 | 49-14-11 | D01796C | 6 | | | D41676J | 13 | | | 115-199 |
| 0341 | 22 | GA | | | 5-0 | 49-72-11 | D41662J | 9 | | | TB0300Y | A004 | BJ | | 115-199 |
| 0343 | 22 | GA | | | 5-0 | 49-61-14 | D01796B | B07 | | | D41676J | 14 | | | 115-199 |
| 0344 | 22 | GA | | | 5-0 | 49-41-11 | D01796C | 1 | | | D41662J | 22 | | | 115-199 |
| 0370 | 22 | GA | | | 5-0 | 24-22-41 | D01796B | J06 | | | D41662J | 1 | | | 115-199 |
| 0371 | 24 | GK | | | 5-0 | 24-27-41 | D41662J | 10 | | | TB0300A | A001 | 2 | | 115-199 |
| 0372 | 24 | GK | | | 2-0 | 24-27-41 | TB0300A | C001 | 2 | | TB0300Y | A004 | BJ | | 115-199 |
| 0373 | 22 | GA | | | 4-0 | 32-42-11 | D02744A | D01 | | | D41686J | 32 | | | 115-199 |
| 0374 | 22 | GA | | | 4-0 | 32-42-11 | D02744B | D01 | | | D41686J | 33 | | | 115-199 |
| 0375 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | C15 | | | GD02440 | DC.. | 2 | | 115-199 |
| 0376 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | C02 | | | GD02440 | DC.. | 2 | | 115-199 |
| 0377 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | C13 | | | GD02440 | DC.. | 2 | | 115-199 |
| 0378 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | C05 | | | D42180J | 13 | | | 115-199 |
| 0379 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | C01 | | | D42180J | 18 | | | 115-199 |
| 0380 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | D05 | | | D42180J | 19 | | | 115-199 |
| 0382 | 20 | GA | | | 4-0 | 32-42-11 | D42184J | | | AB | GD02443 | ST.. | 2 | | 115-199 |
| 0384 | 22 | GA | | | 3-0 | 32-42-11 | D02744A | C05 | | | D42180J | 16 | | | 115-199 |
| 0385 | 22 | GA | | | 3-0 | 32-42-11 | D02744A | D05 | | | D42218J | 2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 7

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1032 | 286N1032 | | | E6-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0386 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | C01 | | D42218J | | 3 | | 115-199 |
| 0387 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | D06 | | D42218J | | 4 | | 115-199 |
| 0388 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | C03 | | D42218J | | 5 | | 115-199 |
| 0389 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | C11 | | D42218J | | 6 | | 115-199 |
| 0390 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | C15 | | GD02440 | DC.. | 2 | | 115-199 |
| 0391 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | C02 | | GD02440 | DC.. | 2 | | 115-199 |
| 0392 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | C04 | | GD02440 | DC.. | 2 | | 115-199 |
| 0393 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | C13 | | GD02441 | DC.. | 2 | | 115-199 |
| 0394 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | A01 | | D41670J | | 10 | | 115-199 |
| 0395 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | A03 | | D41670J | | 14 | | 115-199 |
| 0396 | 22 | | GA | | 4-0 | 32-42-11 | D02744A | | B15 | | D43012J | | 16 | | 115-199 |
| 0397 | 22 | | GA | | 3-0 | 32-42-11 | D02744B | | B01 | | D41670J | | 13 | | 115-199 |
| 0398 | 22 | | GA | | 3-0 | 32-42-11 | D02744B | | B03 | | D41670J | | 15 | | 115-199 |
| 0399 | 22 | | GA | | 4-0 | 32-42-11 | D02744B | | A15 | | D43012J | | 17 | | 115-199 |
| 0400 | 22 | | GA | | 4-0 | 32-42-11 | D02744B | | B15 | | D43014J | | 30 | | 115-199 |
| 0401 | 22 | | GA | | 3-0 | 32-42-11 | D02744B | | A01 | | D41672J | | 15 | | 115-199 |
| 0402 | 22 | | GA | | 3-0 | 32-42-11 | D02744B | | A03 | | D41672J | | 16 | | 115-199 |
| 0403 | 22 | | GA | | 4-0 | 32-42-11 | D02744A | | A15 | | D43014J | | 17 | | 115-199 |
| 0404 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | B01 | | D41672J | | 18 | | 115-199 |
| 0405 | 22 | | GA | | 3-0 | 32-42-11 | D02744A | | B03 | | D41672J | | 19 | | 115-199 |
| 0406 | 20 | | GA | | 4-0 | 32-42-11 | D41670J | | | AC | GD02442 | ST.. | 2 | | 115-199 |
| 0407 | 20 | | GA | | 4-0 | 32-42-11 | D41674J | | | AD | GD02443 | ST.. | 2 | | 115-199 |
| 0408 | 20 | | GA | | 4-0 | 32-42-11 | D41668J | | | AE | GD02442 | ST.. | 2 | | 115-199 |
| 0409 | 20 | | GA | | 4-0 | 32-42-11 | D41672J | | | AF | GD02443 | ST.. | 2 | | 115-199 |
| 0410 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | A08 | | D42180J | | 15 | | 115-199 |
| 0411 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | C08 | | D42180J | | 17 | | 115-199 |
| 0412 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | C14 | | D41833J | | 1 | | 115-199 |
| 0413 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | D07 | | D41833J | | 2 | | 115-199 |
| 0414 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | D08 | | D41833J | | 3 | | 115-199 |
| 0415 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | D09 | | D41833J | | 4 | | 115-199 |
| 0416 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | D10 | | D41833J | | 5 | | 115-199 |
| 0417 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | D11 | | D41833J | | 6 | | 115-199 |
| 0418 | 22 | | GA | | 3-0 | 32-42-12 | TB0300Y | C004 | BJ | | D41833J | | 7 | | 115-199 |
| 0419 | 22 | | GA | | 3-0 | 32-42-12 | D41833J | | 8 | | TB0300Y | C003 | BJ | | 115-199 |
| 0420 | 22 | | GA | | 3-0 | 32-42-12 | D02744A | | D07 | | D41833J | | 9 | | 115-199 |
| 0421 | 22 | | GA | | 3-0 | 32-42-12 | D02744A | | A08 | | D42184J | | 25 | | 115-199 |
| 0422 | 22 | | GA | | 3-0 | 32-42-12 | D02744A | | C08 | | D42184J | | 26 | | 115-199 |
| 0423 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | B09 | | D42184J | | 35 | | 115-199 |
| 0424 | 22 | | GA | | 3-0 | 32-42-12 | D02744B | | A04 | | D42184J | | 27 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 8

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|-----|--------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1032 | 286N1032 | | | | E6-4 SHELF HARNESS (continued) | | | | | | | | | | | | |
| 0425 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | A07 | | | | D42184J | 28 | | | 115-199 | |
| 0426 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | D06 | | | | D42184J | 29 | | | 115-199 | |
| 0427 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | A02 | | | | D42184J | 30 | | | 115-199 | |
| 0428 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | C11 | | | | D42184J | 38 | | | 115-199 | |
| 0429 | 22 | GA | | | 3-0 | 32-42-12 | D02744A | A07 | | | | D42184J | 37 | | | 115-199 | |
| 0430 | 22 | GA | | | 3-0 | 32-42-12 | D41672J | 23 | | | | TB0300Y | C003 | BJ | | 115-199 | |
| 0431 | 22 | GA | | | 3-0 | 32-42-12 | D02744A | A10 | | | | D41670J | 11 | | | 115-199 | |
| 0432 | 22 | GA | | | 3-0 | 32-42-12 | D02744A | B10 | | | | D41670J | 12 | | | 115-199 | |
| 0433 | 22 | GA | | | 3-0 | 32-42-12 | D02744A | C07 | | | | D41672J | 20 | | | 115-199 | |
| 0434 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | A10 | | | | D41672J | 21 | | | 115-199 | |
| 0435 | 22 | GA | | | 3-0 | 32-42-12 | D02744A | B08 | | | | D41672J | 22 | | | 115-199 | |
| 0436 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | D04 | | | | TB0300Y | C003 | BJ | | 115-199 | |
| 0437 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | B08 | | | | D41672J | 24 | | | 115-199 | |
| 0438 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | A09 | | | | D41672J | 25 | | | 115-199 | |
| 0439 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | D12 | | | | D41833J | 10 | | | 115-199 | |
| 0450 | 24 | GK | | | 5-0 | 36-11-41 | D01796B | D03 | | | | D41662J | 2 | | | 115-199 | |
| 0454 | 22 | GA | | | 4-0 | 32-44-11 | D02744A | D15 | | | | D41686J | 14 | | | 115-199 | |
| 0455 | 22 | GA | | | 3-0 | 32-42-12 | D02744B | C03 | | | | TB0300Y | C004 | BJ | | 115-199 | |
| 0456 | 22 | GA | | | 3-0 | 32-42-12 | TB0300Y | C004 | BJ | | | D02744B | C12 | | | 115-199 | |
| 0457 | 22 | GA | | | 3-0 | 32-42-12 | D41833J | 12 | | | | D02744B | C07 | | | 115-199 | |
| 0458 | 22 | GA | | | 3-0 | 32-42-12 | D41833J | 11 | | | | D02744B | C09 | | | 115-199 | |
| 0459 | 22 | GA | | | 3-0 | 32-42-12 | D41833J | 13 | | | | D02744B | C10 | | | 115-199 | |
| 0460 | 22 | GA | | | 3-0 | 32-42-11 | D42180J | 9 | | | | D02744B | A11 | | | 115-199 | |
| 0461 | 22 | GA | | | 3-0 | 32-42-11 | D02744A | C06 | | | | GD02440 | DC.. | 2 | | 115-199 | |
| 0500 | 24 | GK | | | 4-0 | 21-51-11 | D01796B | D05 | | | | D42180J | 30 | | | 115-199 | |
| 0505 | 22 | GA | | | 3-0 | 32-42-12 | D41672J | | | DA | | GD02442 | ST.. | 2 | | 115-199 | |
| 0510 | 22 | GA | | | 5-0 | 49-61-11 | D01796B | D07 | | | | D41662J | 16 | | | 115-199 | |
| 0521 | 22 | GA | | | 4-0 | 29-33-11 | D02598A | B08 | | | | GD02442 | AC.. | 2 | | 115-199 | |
| 0522 | 22 | GA | | | 4-0 | 29-33-11 | D02598B | B11 | | | | GD02442 | AC.. | 2 | | 115-199 | |
| 0523 | 22 | GA | | | 4-0 | 29-33-11 | D02598B | B01 | | | | GD02442 | AC.. | 2 | | 115-199 | |
| 0524 | 22 | GA | | | 3-0 | 29-33-11 | D02598B | A15 | | | | GD02443 | ST.. | 2 | | 115-199 | |
| 0525 | 22 | GA | | | 3-0 | 29-33-11 | D02598B | A13 | | | | GD02443 | DC.. | 2 | | 115-199 | |
| 0526 | 22 | GA | | | 3-0 | 29-33-11 | D02598B | A12 | | | | GD02443 | DC.. | 2 | | 115-199 | |
| 0527 | 20 | GA | | | 4-0 | 32-42-11 | D41670J | | | DB | | GD02442 | ST.. | 2 | | 115-199 | |
| 0528 | 20 | GA | | | 3-0 | 32-42-11 | D41674J | | | DC | | GD02442 | ST.. | 2 | | 115-199 | |
| 0529 | 20 | GA | | | 4-0 | 32-42-11 | D41668J | | | DD | | GD02442 | ST.. | 2 | | 115-199 | |
| 0530 | 20 | GA | | | 3-0 | 32-42-11 | D41672J | | | DE | | GD02442 | ST.. | 2 | | 115-199 | |
| 1001 | 24 | G1 | CX | | 3-0 | 29-33-11 | D40518J | 1 | | | | D02598B | B05 | | | 115-199 | |
| 1001Z | | | CX | | 0-0 | 29-33-11 | D40518J | = C1 | | | | D02598B | C04 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 9

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1032 | 286N1032 | | | E6-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 1002 | 24 | | G1 | CY | 3-0 | 29-33-11 | D40480J | | 1 | | D02598A | B11 | | | 115-199 |
| 1002Z | | | | CY | 0-0 | 29-33-11 | D40480J | = | C1 | | D02598A | C10 | | | 115-199 |
| 1003 | 24 | | G1 | CZ | 3-0 | 29-33-11 | D40464J | | 1 | | D02598A | B02 | | | 115-199 |
| 1003Z | | | | CZ | 0-0 | 29-33-11 | D40464J | = | C1 | | D02598A | C02 | | | 115-199 |
| 2001B | 24 | | GL | AL | 4-0 | 21-61-51 | D01796B | | D08 | | D42180J | 32 | | | 115-199 |
| 2001R | 24 | | GL | AL | 0-0 | 21-61-51 | D01796B | | D09 | | D42180J | 31 | | | 115-199 |
| 2101B | 24 | | GL | AA | 5-0 | 49-71-11 | D01796B | | K04 | | D41662J | 17 | | | 115-199 |
| 2101R | 24 | | GL | AA | 0-0 | 49-71-11 | D01796B | | K05 | | D41662J | 18 | | | 115-199 |
| 2102B | 24 | | GL | AB | 5-0 | 49-73-11 | D01796B | | K07 | | D41662J | 20 | | | 115-199 |
| 2102R | 24 | | GL | AB | 0-0 | 49-73-11 | D01796B | | K08 | | D41662J | 21 | | | 115-199 |
| 2501B | 22 | | GU | BA | 3-0 | 49-14-11 | D01796B | | E04 | | D41678J | 5 | | | 115-199 |
| 2501R | 22 | | GU | BA | 0-0 | 49-14-11 | D01796B | | E05 | | D41678J | 6 | | | 115-199 |
| 2501Z | | | | BA | 0-0 | 49-14-11 | D01796B | | | AJ | D41678J | | | AI | 115-199 |
| 2502B | 22 | | GU | BB | 3-0 | 49-14-11 | D01796B | | B03 | | D41678J | 1 | | | 115-199 |
| 2502R | 22 | | GU | BB | 0-0 | 49-14-11 | D01796B | | B04 | | D41678J | 2 | | | 115-199 |
| 2502Z | | | | BB | 0-0 | 49-14-11 | D01796B | | | AJ | D41678J | | | AI | 115-199 |
| 2503B | 22 | | GU | BC | 3-0 | 49-14-11 | D01796B | | C08 | | D41678J | 3 | | | 115-199 |
| 2503R | 22 | | GU | BC | 0-0 | 49-14-11 | D01796B | | C09 | | D41678J | 4 | | | 115-199 |
| 2503Z | | | | BC | 0-0 | 49-14-11 | D01796B | | | AJ | D41678J | | | AI | 115-199 |
| 2504B | 22 | | GU | BD | 5-0 | 49-14-11 | D01796B | | G08 | | D41676J | 19 | | | 115-199 |
| 2504R | 22 | | GU | BD | 0-0 | 49-14-11 | D01796B | | G09 | | D41676J | 20 | | | 115-199 |
| 2504Z | | | | BD | 0-0 | 49-14-11 | D01796B | | | AK | D41676J | | | AG | 115-199 |
| 2505B | 22 | | GU | BE | 5-0 | 49-14-11 | D01796B | | F11 | | D41676J | 21 | | | 115-199 |
| 2505R | 22 | | GU | BE | 0-0 | 49-14-11 | D01796B | | F08 | | D41676J | 22 | | | 115-199 |
| 2505Z | | | | BE | 0-0 | 49-14-11 | D01796B | | | AK | D41676J | | | AG | 115-199 |
| 2506B | 22 | | GU | BF | 5-0 | 49-14-11 | D01796B | | F09 | | D41676J | 23 | | | 115-199 |
| 2506R | 22 | | GU | BF | 0-0 | 49-14-11 | D01796B | | F10 | | D41676J | 24 | | | 115-199 |
| 2506Z | | | | BF | 0-0 | 49-14-11 | D01796B | | | AK | D41676J | | | AG | 115-199 |
| 2507B | 22 | | GU | BG | 5-0 | 49-14-11 | D01796B | | H10 | | D41676J | 25 | | | 115-199 |
| 2507R | 22 | | GU | BG | 0-0 | 49-14-11 | D01796B | | H11 | | D41676J | 26 | | | 115-199 |
| 2507Z | | | | BG | 0-0 | 49-14-11 | D01796B | | | AK | D41676J | | | AG | 115-199 |
| 2508B | 22 | | GU | BH | 4-0 | 49-14-11 | D01796B | | G06 | | D41676J | 27 | | | 115-199 |
| 2508R | 22 | | GU | BH | 0-0 | 49-14-11 | D01796B | | G07 | | D41676J | 28 | | | 115-199 |
| 2508Z | | | | BH | 0-0 | 49-14-11 | D01796B | | | AK | D41676J | | | AG | 115-199 |
| 2512B | 22 | | GU | BL | 5-0 | 49-14-11 | D01796B | | A10 | | D41676J | 30 | | | 115-199 |
| 2512R | 22 | | GU | BL | 0-0 | 49-14-11 | D01796B | | A11 | | D41676J | 31 | | | 115-199 |
| 2512Z | | | | BL | 0-0 | 49-14-11 | D01796B | | | AL | D41676J | | | AH | 115-199 |
| 2513B | 22 | | GU | BM | 5-0 | 49-14-11 | D01796B | | B05 | | D41676J | 32 | | | 115-199 |
| 2513R | 22 | | GU | BM | 0-0 | 49-14-11 | D01796B | | B06 | | D41676J | 33 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 10

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|--------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1032 | 286N1032 | | | E6-4 SHELF HARNESS (continued) | | | | | | | | | | | | |
| 2513Z | | | | BM | 0-0 | 49-14-11 | D01796B | | | | AL | D41676J | | | AH | 115-199 |
| 2514B | | 22 | | GU BN | 3-0 | 32-42-11 | D02744B | | B06 | | | D41670J | 1 | | | 115-199 |
| 2514R | | 22 | | GU BN | 0-0 | 32-42-11 | D02744B | | B05 | | | D41670J | 2 | | | 115-199 |
| 2514Z | | | | BN | 0-0 | 32-42-11 | D02744B | | DED | | | D41670J | | | AC | 115-199 |
| 2515B | | 22 | | GU BO | 3-0 | 32-42-11 | D02744B | | B13 | | | D41670J | 3 | | | 115-199 |
| 2515R | | 22 | | GU BO | 0-0 | 32-42-11 | D02744B | | B12 | | | D41670J | 4 | | | 115-199 |
| 2515Z | | | | BO | 0-0 | 32-42-11 | D02744B | | DED | | | D41670J | | | DB | 115-199 |
| 2516B | | 22 | | GU BP | 3-0 | 32-42-11 | D02744A | | A06 | | | D41674J | 1 | | | 115-199 |
| 2516R | | 22 | | GU BP | 0-0 | 32-42-11 | D02744A | | A05 | | | D41674J | 2 | | | 115-199 |
| 2516Z | | | | BP | 0-0 | 32-42-11 | D02744A | | DED | | | D41674J | | | AD | 115-199 |
| 2517B | | 22 | | GU BQ | 3-0 | 32-42-11 | D02744A | | A13 | | | D41674J | 3 | | | 115-199 |
| 2517R | | 22 | | GU BQ | 0-0 | 32-42-11 | D02744A | | A12 | | | D41674J | 4 | | | 115-199 |
| 2517Z | | | | BQ | 0-0 | 32-42-11 | D02744A | | DED | | | D41674J | | | DC | 115-199 |
| 2518B | | 22 | | GU BR | 4-0 | 32-42-11 | D02744B | | A06 | | | D41668J | 1 | | | 115-199 |
| 2518R | | 22 | | GU BR | 0-0 | 32-42-11 | D02744B | | A05 | | | D41668J | 2 | | | 115-199 |
| 2518Z | | | | BR | 0-0 | 32-42-11 | D02744B | | DED | | | D41668J | | | AE | 115-199 |
| 2519B | | 22 | | GU BS | 4-0 | 32-42-11 | D02744B | | A13 | | | D41668J | 3 | | | 115-199 |
| 2519R | | 22 | | GU BS | 0-0 | 32-42-11 | D02744B | | A12 | | | D41668J | 4 | | | 115-199 |
| 2519Z | | | | BS | 0-0 | 32-42-11 | D02744B | | DED | | | D41668J | | | DD | 115-199 |
| 2520B | | 22 | | GU BT | 3-0 | 32-42-11 | D02744A | | B06 | | | D41672J | 9 | | | 115-199 |
| 2520R | | 22 | | GU BT | 0-0 | 32-42-11 | D02744A | | B05 | | | D41672J | 10 | | | 115-199 |
| 2520Z | | | | BT | 0-0 | 32-42-11 | D02744A | | DED | | | D41672J | | | AF | 115-199 |
| 2521B | | 22 | | GU BU | 3-0 | 32-42-11 | D02744A | | B13 | | | D41672J | 3 | | | 115-199 |
| 2521R | | 22 | | GU BU | 0-0 | 32-42-11 | D02744A | | B12 | | | D41672J | 5 | | | 115-199 |
| 2521Z | | | | BU | 0-0 | 32-42-11 | D02744A | | DED | | | D41672J | | | DE | 115-199 |
| 2522B | | 22 | | GU BV | 3-0 | 32-42-12 | D02744A | | C09 | | | D41672J | 11 | | | 115-199 |
| 2522R | | 22 | | GU BV | 0-0 | 32-42-12 | D02744A | | D09 | | | D41672J | 12 | | | 115-199 |
| 2522Z | | | | BV | 0-0 | 32-42-12 | D02744A | | DED | | | D41672J | | | DA | 115-199 |
| 4251B | | 22 | | GW VA | 3-0 | 49-14-11 | D01796B | | A01 | | | D41678J | 8 | | | 115-199 |
| 4251G | | 22 | | GW VA | 0-0 | 49-14-11 | D01796B | | A02 | | | D41678J | 9 | | | 115-199 |
| 4251R | | 22 | | GW VA | 0-0 | 49-14-11 | D01796B | | A03 | | | D41678J | 10 | | | 115-199 |
| 4251Y | | 22 | | GW VA | 0-0 | 49-14-11 | D01796B | | A04 | | | D41678J | 11 | | | 115-199 |
| 4251Z | | | | VA | 0-0 | 49-14-11 | D01796B | | | | AJ | D41678J | | | AI | 115-199 |
| 4501G | | 22 | | XU TA | 4-0 | 32-46-11 | D02794A | | A02 | 62 | | D41668J | 7 | | | 115-199 |
| 4501W | | 22 | | XU TA | 0-0 | 32-46-11 | D02794A | | A01 | 63 | | D41668J | 8 | | | 115-199 |
| 4502G | | 22 | | XU TB | 4-0 | 32-46-11 | D02794A | | A05 | 62 | | D41668J | 9 | | | 115-199 |
| 4502W | | 22 | | XU TB | 0-0 | 32-46-11 | D02794A | | A04 | 63 | | D41668J | 10 | | | 115-199 |
| 4503G | | 22 | | XU TC | 3-0 | 32-46-11 | D02794A | | A14 | 62 | | D41672J | 2 | | | 115-199 |
| 4503W | | 22 | | XU TC | 0-0 | 32-46-11 | D02794A | | A13 | 63 | | D41672J | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 11

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1032 | 286N1032 | | | | E6-4 SHELF HARNESS (continued) | | | | | | | | | | | | |
| 4504G | 22 | XU | TD | | 3-0 | 32-46-11 | D02794A | C02 | 62 | | | D41672J | 14 | | | 115-199 | |
| 4504W | 22 | XU | TD | | 0-0 | 32-46-11 | D02794A | C01 | 63 | | | D41672J | 13 | | | 115-199 | |
| 4505G | 22 | XU | TE | | 3-0 | 32-46-11 | D02794A | A08 | 62 | | | D41670J | 6 | | | 115-199 | |
| 4505W | 22 | XU | TE | | 0-0 | 32-46-11 | D02794A | A07 | 63 | | | D41670J | 7 | | | 115-199 | |
| 4506G | 22 | XU | TF | | 3-0 | 32-46-11 | D02794A | A11 | 62 | | | D41670J | 8 | | | 115-199 | |
| 4506W | 22 | XU | TF | | 0-0 | 32-46-11 | D02794A | A10 | 63 | | | D41670J | 9 | | | 115-199 | |
| 4507G | 22 | XU | TG | | 3-0 | 32-46-11 | D02794A | C05 | 62 | | | D41674J | 6 | | | 115-199 | |
| 4507W | 22 | XU | TG | | 0-0 | 32-46-11 | D02794A | C04 | 63 | | | D41674J | 7 | | | 115-199 | |
| 4508G | 22 | XU | TH | | 3-0 | 32-46-11 | D02794A | C08 | 62 | | | D41674J | 8 | | | 115-199 | |
| 4508W | 22 | XU | TH | | 0-0 | 32-46-11 | D02794A | C07 | 63 | | | D41674J | 9 | | | 115-199 | |
| 4601G | 22 | DU | TP | | 5-0 | 49-14-11 | D01796B | A06 | | | | D41676J | 34 | | | 115-199 | |
| 4601W | 22 | DU | TP | | 0-0 | 49-14-11 | D01796B | A07 | | | | D41676J | 35 | | | 115-199 | |
| 4601Z | | | TP | | 0-0 | 49-14-11 | D01796B | | | | AL | D41676J | | | AH | 115-199 | |
| 4602G | 22 | DU | TQ | | 5-0 | 49-14-11 | D01796B | A08 | | | | D41676J | 36 | | | 115-199 | |
| 4602W | 22 | DU | TQ | | 0-0 | 49-14-11 | D01796B | A09 | | | | D41676J | 37 | | | 115-199 | |
| 4602Z | | | TQ | | 0-0 | 49-14-11 | D01796B | | | | AL | D41676J | | | AH | 115-199 | |
| 4603G | 22 | DU | TR | | 5-0 | 49-14-11 | D01796B | E06 | | | | D41676J | 38 | | | 115-199 | |
| 4603W | 22 | DU | TR | | 0-0 | 49-14-11 | D01796B | E07 | | | | D41676J | 39 | | | 115-199 | |
| 4603Z | | | TR | | 0-0 | 49-14-11 | D01796B | | | | AL | D41676J | | | AH | 115-199 | |
| 5001B | 22 | GU | ZA | | 3-0 | 32-42-11 | D02744A | D12 | | | | D42180J | 11 | | | 115-199 | |
| 5001R | 22 | GU | ZA | | 0-0 | 32-42-11 | D02744A | D11 | | | | D42180J | 10 | | | 115-199 | |
| 5001Z | | | ZA | | 0-0 | 32-42-11 | GD02441 | ST.. | 2 | | | D42180J | 12 | | | 115-199 | |
| 5002B | 22 | GU | ZB | | 3-0 | 32-42-11 | D02744B | D14 | | | | D42184J | 11 | | | 115-199 | |
| 5002R | 22 | GU | ZB | | 0-0 | 32-42-11 | D02744B | D13 | | | | D42184J | 10 | | | 115-199 | |
| 5002Z | | | ZB | | 0-0 | 32-42-11 | D02744B | DED | | | | D42184J | | | AB | 115-199 | |
| FRAB | | | | | 0-0 | 32-42-11 | D42184J | 12 | | | | D42184J | | | AB | 115-199 | |
| FRAC | | | | | 0-0 | 32-42-11 | D41670J | 5 | | | | D41670J | | | AC | 115-199 | |
| FRAD | | | | | 0-0 | 32-42-11 | D41674J | 5 | | | | D41674J | | | AD | 115-199 | |
| FRAE | | | | | 0-0 | 32-42-11 | D41668J | 5 | | | | D41668J | | | AE | 115-199 | |
| FRAF | | | | | 0-0 | 32-42-11 | D41672J | 4 | | | | D41672J | | | AF | 115-199 | |
| FRAG | | | | | 0-0 | 49-14-11 | D41676J | 29 | | | | D41676J | | | AG | 115-199 | |
| FRAH | | | | | 0-0 | 49-14-11 | D41676J | 40 | | | | D41676J | | | AH | 115-199 | |
| FRAI | | | | | 0-0 | 49-14-11 | D41678J | 7 | | | | D41678J | | | AI | 115-199 | |
| FRAJ | | | | | 0-0 | 49-14-11 | D01796B | J09 | | | | D01796B | | | AJ | 115-199 | |
| FRAK | | | | | 0-0 | 32-42-11 | D41670J | 18 | | | | D41670J | | | DB | 115-199 | |
| FRAL | | | | | 0-0 | 32-42-11 | D41674J | 10 | | | | D41674J | | | DC | 115-199 | |
| FRAM | | | | | 0-0 | 32-42-11 | D41668J | 11 | | | | D41668J | | | DD | 115-199 | |
| FRAN | | | | | 0-0 | 32-42-11 | D41672J | 6 | | | | D41672J | | | DE | 115-199 | |
| FRDA | | | | | 0-0 | 32-42-12 | D41672J | 7 | | | | D41672J | | | DA | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1030

Page 12 End

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|----|-------|-------------|-------|------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1115 | | | | | | P10-MODULE WIRE | | | | | | | | | |
| 0200 | 22 | GA | | | 0-0 | 76-11-11 | D02146 | 24 | | | D40901J | 4 | | | ALL |
| 0201 | 22 | GA | | | 0-0 | 33-16-51 | TB0190Y | A009 | BJ | | D02146 | 4 | | | ALL |
| 0202 | 22 | GA | | | 0-0 | 33-16-51 | D02146 | 3 | | | D40899J | 10 | | | ALL |
| 0204 | 22 | GA | | | 0-0 | 26-11-11 | D02146 | 6 | | | D40901J | 1 | | | ALL |
| 0205 | 22 | GA | | | 0-0 | 76-11-11 | D02146 | 7 | | | SM00005 | | WI | | ALL |
| 0206 | 22 | GA | | | 0-0 | 28-22-21 | D02146 | 8 | | | D40901J | 11 | | | ALL |
| 0208 | 22 | GA | | | 0-0 | 28-22-21 | D02146 | 10 | | | D40901J | 12 | | | ALL |
| 0209 | 22 | GA | | | 0-0 | 76-11-11 | D02146 | 11 | | | D40901J | 14 | | | ALL |
| 0210 | 22 | GA | | | 0-0 | 76-11-11 | D02146 | 12 | | | D40901J | 13 | | | ALL |
| 0211 | 22 | GA | | | 0-0 | 76-11-11 | SM00005 | | WI | | D40901J | 15 | | | ALL |
| 0212 | 22 | GA | | | 0-0 | 28-22-21 | D02146 | 14 | | | D40901J | 26 | | | ALL |
| 0213 | 20 | GA | | | 0-0 | 28-22-21 | D02146 | 15 | | | GD01602 | DC.. | 2 | | ALL |
| 0216Y | 22 | GA | | | 0-0 | 27-41-11 | D02146 | 26 | | | D40901J | 2 | | | ALL |
| 0217Y | 22 | GA | | | 0-0 | 27-41-11 | D02146 | 25 | | | D40901J | 18 | | | ALL |
| 0218Y | 22 | GA | | | 0-0 | 27-41-11 | D02146 | 27 | | | D40901J | 19 | | | ALL |
| 0219 | 22 | GA | | | 0-0 | 28-22-21 | D02146 | 23 | | | D40901J | 24 | | | ALL |
| 0224 | 22 | GA | | | 0-0 | 76-11-11 | D02146 | 22 | | | D40901J | 21 | | | ALL |
| 0250 | 22 | GA | | | 0-0 | 76-11-12 | D02148 | 26 | | | D40899J | 20 | | | ALL |
| 0251 | 22 | GA | | | 0-0 | 33-16-61 | TB0190Y | C003 | BJ | | D02148 | 3 | | | ALL |
| 0252 | 22 | GA | | | 0-0 | 33-16-51 | D02148 | 4 | | | TB0190Y | A009 | BJ | | ALL |
| 0254 | 22 | GA | | | 0-0 | 26-11-21 | D02148 | 6 | | | D40899J | 1 | | | ALL |
| 0255 | 22 | GA | | | 0-0 | 76-11-12 | D02148 | 7 | | | SM00006 | | WI | | ALL |
| 0256 | 22 | GA | | | 0-0 | 28-22-21 | D02148 | 8 | | | D40899J | 11 | | | ALL |
| 0258 | 22 | GA | | | 0-0 | 28-22-21 | D02148 | 10 | | | D40899J | 12 | | | ALL |
| 0259 | 22 | GA | | | 0-0 | 76-11-12 | D02148 | 11 | | | D40899J | 14 | | | ALL |
| 0260 | 22 | GA | | | 0-0 | 76-11-12 | D02148 | 12 | | | D40899J | 13 | | | ALL |
| 0261 | 22 | GA | | | 0-0 | 76-11-12 | SM00006 | | WI | | D40899J | 15 | | | ALL |
| 0262 | 22 | GA | | | 0-0 | 28-22-21 | D02148 | 14 | | | D40899J | 17 | | | ALL |
| 0263 | 20 | GA | | | 0-0 | 28-22-21 | D02148 | 15 | | | GD01602 | DC.. | 2 | | ALL |
| 0266Y | 22 | GA | | | 0-0 | 27-41-21 | D02148 | 24 | | | D40899J | 5 | | | ALL |
| 0267 | 22 | GA | | | 0-0 | 28-22-21 | D02148 | 27 | | | D40899J | 23 | | | ALL |
| 0271 | 22 | GA | | | 0-0 | 76-11-12 | D02148 | 22 | | | D40899J | 4 | | | ALL |
| 0273Y | 22 | GA | | | 0-0 | 27-41-21 | D02148 | 23 | | | D40782J | 8 | | | ALL |
| 0274Y | 22 | GA | | | 0-0 | 27-41-21 | D02148 | 25 | | | D40782J | 9 | | | ALL |
| 0278 | 20 | GA | | | 0-0 | 33-13-51 | D06894 | = A1 | | | TB0192Z | 4 | BJ | | ALL |
| 0279 | 20 | GA | | | 0-0 | 33-13-51 | D06896 | = A1 | | | GD01604 | AC.. | 2 | | ALL |
| 0300 | 22 | GA | | | 0-0 | 22-12-11 | D40897J | 5 | | | D40501J | 2 | | | ALL |
| 0301 | 22 | GA | | | 0-0 | 22-12-21 | D40893J | 5 | | | D40495J | 4 | | | ALL |
| 0302 | 22 | GA | | | 0-0 | 22-12-21 | D40893J | 2 | | | D40495J | 3 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1110

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1115 | 286N1115 | | | P10-MODULE WIRE (continued) | | | | | | | | | | | |
| 0303 | 22 | | GA | | 0-0 | 22-12-21 | D40893J | | 1 | | D40893J | | 6 | | ALL |
| 0304 | 22 | | GA | | 0-0 | 78-34-61 | D40893J | | 7 | | D40899J | | 18 | | ALL |
| 0305 | 22 | | GA | | 0-0 | 78-34-61 | D40893J | | 8 | | D40899J | | 6 | | ALL |
| 0310 | 22 | | GA | | 0-0 | 22-12-11 | D40897J | | 4 | | D40501J | | 1 | | ALL |
| 0311 | 22 | | GA | | 0-0 | 22-12-31 | D40895J | | 1 | | D40895J | | 6 | | ALL |
| 0312 | 22 | | GA | | 0-0 | 22-12-31 | D40895J | | 5 | | D40503J | | 2 | | ALL |
| 0321 | 22 | | GA | | 0-0 | 78-34-51 | D40897J | | 9 | | D40901J | | 30 | | ALL |
| 0322 | 22 | | GA | | 0-0 | 78-34-51 | D40897J | | 8 | | D40901J | | 31 | | ALL |
| 0323 | 22 | | GA | | 0-0 | 22-32-15 | D40897J | | 1 | | D40501J | | 4 | | ALL |
| 0324 | 22 | | GA | | 0-0 | 22-32-15 | D40897J | | 11 | | SM00001 | | | WI | ALL |
| 0325 | 22 | | GA | | 0-0 | 22-32-15 | SM00001 | | | WI | D40501J | | 3 | | ALL |
| 0326 | 22 | | GA | | 0-0 | 22-32-15 | D40897J | | 13 | | SM00001 | | | WI | ALL |
| 0327 | 22 | | GA | | 0-0 | 22-32-15 | D40897J | | 12 | | SM00002 | | | WI | ALL |
| 0328 | 22 | | GA | | 0-0 | 22-32-15 | SM00002 | | | WI | D40501J | | 8 | | ALL |
| 0329 | 22 | | GA | | 0-0 | 22-32-15 | D40897J | | 14 | | SM00002 | | | WI | ALL |
| 0330 | 22 | | GA | | 0-0 | 22-32-15 | D40897J | | 7 | | SM00002 | | | WI | ALL |
| 0331 | 22 | | GA | | 0-0 | 22-12-31 | D40895J | | 2 | | D40503J | | 1 | | ALL |
| 0332 | 22 | | GA | | 0-0 | 22-12-11 | D40897J | | 3 | | D40897J | | 15 | | ALL |
| 0334 | 22 | | GA | | 0-0 | 22-32-15 | D40897J | | 2 | | D40897J | | 6 | | ALL |
| 0350 | 20 | | GA | | 0-0 | 27-62-11 | D03204 | | 12 | | GD01609 | ST.. | E | | ALL |
| 0351 | 20 | | GA | | 0-0 | 27-62-11 | D03204 | | 10 | | GD01601 | DC.. | 2 | | ALL |
| 0352 | 22 | | GA | | 0-0 | 27-62-11 | D03204 | | 6 | | D40501J | | 21 | | ALL |
| 0353 | 22 | | GA | | 0-0 | 27-62-11 | D03204 | | 8 | | D40501J | | 23 | | ALL |
| 0354 | 20 | | GA | | 0-0 | 27-62-11 | D03204 | | 4 | | GD01601 | DC.. | 2 | | ALL |
| 0355 | 22 | | GA | | 0-0 | 27-62-11 | D03204 | | 3 | | TB0190X | A005 | BJ | | ALL |
| 0356 | 22 | | GA | | 0-0 | 27-62-11 | TB0190X | B005 | BJ | | D40495J | | 1 | | ALL |
| 0357 | 22 | | GA | | 0-0 | 27-62-11 | TB0190X | C005 | BJ | | D40495J | | 2 | | ALL |
| 0358 | 22 | | GA | | 0-0 | 27-62-11 | TB0190X | D005 | BJ | | D40501J | | 29 | | ALL |
| 0359 | 22 | | GA | | 0-0 | 27-62-11 | TB0190Y | A003 | BJ | | D40501J | | 15 | | ALL |
| 0360 | 22 | | GA | | 0-0 | 27-62-11 | TB0190Y | A004 | BJ | | D40501J | | 14 | | ALL |
| 0361 | 22 | | GA | | 0-0 | 27-62-11 | TB0190Y | A004 | BJ | | D40501J | | 28 | | ALL |
| 0362 | 22 | | GA | | 0-0 | 33-13-51 | TB0192Z | | 3 | BJ | TB0192Z | | 4 | BJ | ALL |
| 0387 | 22 | | GA | | 0-0 | 32-44-11 | L00413 | | 2 | 1A | TB0190X | B001 | BJ | | ALL |
| 0388 | 22 | | GA | | 0-0 | 33-16-51 | L00413 | | 3 | 1A | TB0190Y | A009 | BJ | | ALL |
| 0389 | 22 | | GA | | 0-0 | 33-16-61 | L00413 | | 1 | 1A | TB0190Y | C003 | BJ | | ALL |
| 0391 | 20 | | GA | | 0-0 | 33-13-51 | TB0192Z | | 3 | BJ | D40784J | | 4 | | ALL |
| 0395 | 22 | | GA | | 0-0 | 28-22-21 | D02146 | | 9 | | D40901J | | 3 | | ALL |
| 0396 | 22 | | GA | | 0-0 | 28-22-21 | D02148 | | 9 | | D40899J | | 19 | | ALL |
| 0397 | 22 | | GA | | 0-0 | 27-62-11 | D40501J | | 34 | | D40501J | | 27 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1110

Page 2

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1115 | | 286N1115 | | | | P10-MODULE WIRE (continued) | | | | | | | | | |
| 0401 | 22 | GA | | | 0-0 | 32-42-12 | TB0190Z | 7 | BJ | | D40495J | 12 | | | ALL |
| 0402 | 22 | GA | | | 0-0 | 32-42-12 | TB0190Z | 7 | BJ | | D40495J | 18 | | | ALL |
| 0406 | 22 | GA | | | 0-0 | 32-42-12 | TB0190Z | 7 | BJ | | D40495J | 6 | | | ALL |
| 0409 | 22 | GA | | | 0-0 | 32-42-12 | TB0190X | B002 | BJ | | D40495J | 17 | | | ALL |
| 0412 | 22 | GA | | | 0-0 | 31-51-41 | TB0190Y | C004 | BJ | | D40495J | 20 | | | ALL |
| 0423 | 22 | GA | | | 0-0 | 32-44-11 | TB0190X | B001 | BJ | | D40784J | 3 | | | ALL |
| 0424 | 22 | GA | | | 0-0 | 33-16-51 | TB0190Y | A009 | BJ | | D40899J | 9 | | | ALL |
| 0425 | 22 | GA | | | 0-0 | 33-16-61 | TB0190Y | C003 | BJ | | D40899J | 8 | | | ALL |
| 0426 | 22 | GA | | | 0-0 | 27-62-11 | TB0190X | A002 | BJ | | TB0190X | C001 | BJ | | ALL |
| 0427 | 22 | GA | | | 0-0 | 27-62-11 | TB0190X | D001 | BJ | | TB0190Y | A003 | BJ | | ALL |
| 0430 | 20 | GA | | | 0-0 | 27-51-41 | D01810 | 7 | | | GD00104 | ST.. | E | | ALL |
| 0434 | 22 | GA | | | 0-0 | 76-11-11 | D02146 | 13 | | | SM00005 | | WI | | ALL |
| 0435 | 22 | GA | | | 0-0 | 76-11-12 | D02148 | 13 | | | SM00006 | | WI | | ALL |
| 0438 | 22 | GA | | | 0-0 | SPARE | TB0192Y | A002 | BJ | | D40503J | 11 | | | 001-099 |
| 0439 | 22 | GA | | | 0-0 | SPARE | TB0192Y | A001 | BJ | | D40503J | 10 | | | 001-099 |
| 0440 | 22 | GA | | | 0-0 | SPARE | TB0190X | A001 | BJ | | D40503J | 24 | | | 001-099 |
| 0440 | 22 | GA | | | 0-0 | 31-31-31 | TB0190X | A001 | BJ | | D40503J | 24 | | | 115-199 |
| 2001B | 22 | GB | AA | | 0-0 | 27-51-41 | D01810 | 2 | | | D40782J | 12 | | | ALL |
| 2001R | 22 | GB | AA | | 0-0 | 27-51-41 | D01810 | 1 | | | D40782J | 5 | | | ALL |
| 2002B | 22 | GB | AC | | 0-0 | SPARE | TB0190X | D002 | BJ | | D40503J | 20 | | | 001-099 |
| 2002B | 22 | GB | AC | | 0-0 | 31-31-31 | TB0190X | D002 | BJ | | D40503J | 20 | | | 115-199 |
| 2002R | 22 | GB | AC | | 0-0 | SPARE | TB0190X | C002 | BJ | | D40503J | 19 | | | 001-099 |
| 2002R | 22 | GB | AC | | 0-0 | 31-31-31 | TB0190X | C002 | BJ | | D40503J | 19 | | | 115-199 |
| 4001B | 22 | GD | AB | | 0-0 | 27-51-41 | D01810 | 4 | | | D40782J | 7 | | | ALL |
| 4001G | 22 | GD | AB | | 0-0 | 27-51-41 | D01810 | 6 | | | D40782J | 11 | | | ALL |
| 4001R | 22 | GD | AB | | 0-0 | 27-51-41 | D01810 | 3 | | | D40782J | 6 | | | ALL |
| 4001Y | 22 | GD | AB | | 0-0 | 27-51-41 | D01810 | 5 | | | D40782J | 10 | | | ALL |
| A-BK | | | | | 0-0 | 32-42-12 | S00493 | BLK | | | TB0190X | B002 | BJ | | ALL |
| A-BU | | | | | 0-0 | 32-42-12 | S00493 | BLU | | | TB0190Z | 7 | BJ | | ALL |
| A-CO | | | | | 0-0 | 27-62-11 | S00371 | C | | | TB0190X | B005 | BJ | | ALL |
| A-N | | | | | 0-0 | 27-62-11 | S00371 | NO | | | TB0190X | C005 | BJ | | ALL |
| A-NC | | | | | 0-0 | 27-62-11 | S00371 | NC | | | TB0190X | A005 | BJ | | ALL |
| A-RD | | | | | 0-0 | 32-42-12 | S00493 | RED | | | TB0190X | CAP | Y | | ALL |
| B-BK | | | | | 0-0 | 31-51-41 | S00493 | BLK | | | TB0190Y | C004 | BJ | | ALL |
| B-BU | | | | | 0-0 | 31-51-41 | S00493 | BLU | | | GD01601 | DC.. | 2 | | ALL |
| B-CO | | | | | 0-0 | 27-62-11 | S00371 | C | | | TB0190X | D005 | BJ | | ALL |
| B-N | | | | | 0-0 | 27-62-11 | S00371 | NO | | | TB0190Y | A003 | BJ | | ALL |
| B-NC | | | | | 0-0 | 27-62-11 | S00371 | NC | | | TB0190X | A002 | BJ | | ALL |
| B-RD | | | | | 0-0 | 31-51-41 | TB0190Y | CAP | Y | | S00493 | RED | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1110

Page 3

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1115 | 286N1115 | | | P10-MODULE WIRE (continued) | | | | | | | | | | | |
| C-CO | | | | | 0-0 | 27-62-11 | S00374 | | C | | TB0190X | C001 | BJ | | ALL |
| C-NC | | | | | 0-0 | 27-62-11 | S00374 | | NC | | TB0190Y | A004 | BJ | | ALL |
| C-NO | | | | | 0-0 | 27-62-11 | S00374 | | NO | | TB0190X | D001 | BJ | | ALL |
| G-95 | | | | | 0-0 | 33-13-51 | L00495 | | WHT | | GD01604 | AC.. | 2 | | ALL |
| G-97 | | | | | 0-0 | 33-13-51 | L00497 | | WHT | | GD01604 | AC.. | 2 | | ALL |
| G-98 | | | | | 0-0 | 33-13-51 | L00498 | | WHT | | GD01604 | AC.. | 2 | | ALL |
| G-99 | | | | | 0-0 | 33-13-51 | L00499 | | WHT | | GD01604 | AC.. | 2 | | ALL |
| L-FC | | | | | 0-0 | 33-13-51 | L00499 | | BLK | | TB0192Z | 3 | BJ | | ALL |
| L-FL | | | | | 0-0 | 33-13-51 | L00497 | | BLK | | TB0192Z | 4 | BJ | | ALL |
| L-SB | | | | | 0-0 | 33-13-51 | L00498 | | BLK | | TB0192Z | 4 | BJ | | ALL |
| L-ST | | | | | 0-0 | 33-13-51 | L00495 | | BLK | | TB0192Z | 3 | BJ | | ALL |
| M-BK | | | | | 0-0 | 31-31-31 | TS0352 | | BLK | | GD01603 | AC.. | 2 | | 115-199 |
| M-BU | | | | | 0-0 | 31-31-31 | TS0352 | | BLU | | GD01603 | AC.. | 2 | | 115-199 |
| M-GN | | | | | 0-0 | 31-31-31 | TS0352 | | GRN | | TB0190X | D002 | BJ | | 115-199 |
| M-RD | | | | | 0-0 | 31-31-31 | TS0352 | | RED | | TB0190X | A001 | BJ | | 115-199 |
| M-YL | | | | | 0-0 | 31-31-31 | TS0352 | | YEL | | TB0190X | C002 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1110

Page 4 End

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|----|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1120 | 286N1120 | | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET | | | | | | | | | | | | |
| 0001 | 24 | | 1E | | 3-0 | 26-11-11 | | D41936J | 15 | | | TB0069Z | 1 | BJ | | 001-099 | |
| 0001 | 22 | | 1E | | 3-0 | 26-11-11 | | D01598 | 18 | | | GD02040 | DC.. | 2 | | 115-199 | |
| 0002 | 24 | | 1E | | 2-0 | 26-11-11 | | D41944J | 22 | | | TB0069Z | 9 | BJ | | 001-099 | |
| 0002 | 22 | | 1E | | 3-0 | 26-11-11 | | D01598 | 3 | | | GD02040 | DC.. | 2 | | 115-199 | |
| 0003 | 24 | | 1E | | 3-0 | 26-11-11 | | D01598 | 1 | | | TB0069Z | 9 | BJ | | 001-099 | |
| 0003 | 24 | | 1E | | 2-0 | 26-11-11 | | D01598 | 10 | | | D01822 | 48 | | | 115-199 | |
| 0004 | 22 | | 1E | | 3-0 | 26-11-11 | | D01598 | 18 | | | GD02040 | DC.. | 2 | | 001-099 | |
| 0004 | 24 | | 1E | | 2-0 | 26-11-11 | | D01598 | 6 | | | D01822 | 44 | | | 115-199 | |
| 0005 | 22 | | 1E | | 3-0 | 26-11-11 | | D01598 | 3 | | | GD02040 | DC.. | 2 | | 001-099 | |
| 0005 | 24 | | 1E | | 2-0 | 26-11-11 | | D01598 | 14 | | | D01822 | 9 | | | 115-199 | |
| 0006 | 24 | | 1E | | 3-0 | 26-11-11 | | D01598 | 20 | | | D41944J | 9 | | | 001-099 | |
| 0006 | 24 | | 1E | | 2-0 | 26-11-11 | | D01598 | 16 | | | D01822 | 3 | | | 115-199 | |
| 0007 | 24 | | 1E | | 3-0 | 26-11-11 | | D01598 | 19 | | | D41944J | 38 | | | 001-099 | |
| 0007 | 24 | | 1E | | 3-0 | 26-11-11 | | TB0069Z | 1 | BJ | | D01822 | 1 | | | 115-199 | |
| 0008 | 24 | | 1E | | 3-0 | 26-11-11 | | D01598 | 21 | | | D41944J | 11 | | | 001-099 | |
| 0008 | 24 | | 1E | | 0-3 | 26-11-11 | | SM00010 | | WI | | D01822 | 49 | | | 115-199 | |
| 0009 | 24 | | 1E | | 3-0 | 26-11-11 | | D01596 | 1 | | | TB0069Z | 1 | BJ | | 001-099 | |
| 0009 | 24 | | 1E | | 0-3 | 26-11-11 | | SM00010 | | WI | | D01822 | 16 | | | 115-199 | |
| 0010 | 24 | | 1E | | 3-0 | 26-11-11 | | D01596 | 20 | | | D41936J | 13 | | | 001-099 | |
| 0010 | 22 | | 1E | | 0-5 | 26-11-11 | | GD03130 | DC.. | E | *1 | D01822 | 50 | | | 115-199 | |
| 0011 | 24 | | 1E | | 3-0 | 26-11-11 | | D01596 | 19 | | | D41936J | 10 | | | 001-099 | |
| 0011 | 24 | | 1E | | 2-0 | 26-11-11 | | D41944J | 8 | | | SM00012 | | WI | | 115-199 | |
| 0012 | 24 | | 1E | | 3-0 | 26-11-11 | | D01596 | 21 | | | D41936J | 1 | | | 001-099 | |
| 0012 | 24 | | 1E | | 3-0 | 26-11-11 | | D01822 | 2 | | | TB0069Z | 9 | BJ | | 115-199 | |
| 0013 | 22 | | 1E | | 3-0 | 26-11-11 | | D01596 | 3 | | | GD01047 | DC.. | 2 | | 001-099 | |
| 0013 | 24 | | 1E | | 0-3 | 26-11-11 | | D01822 | 4 | | | SM00010 | | WI | | 115-199 | |
| 0014 | 22 | | 1E | | 3-0 | 26-11-11 | | D01596 | 18 | | | GD01047 | DC.. | 2 | | 001-099 | |
| 0014 | 22 | | 1E | | 0-5 | 26-11-11 | | D01822 | 46 | | | GD03130 | DC.. | E | *1 | 115-199 | |
| 0015 | 22 | | 1E | | 0-5 | 26-11-11 | | D01822 | 14 | | | GD03130 | DC.. | E | *1 | 115-199 | |
| 0017 | 24 | | 1E | | 0-3 | 26-11-11 | | D01822 | 13 | | | D01822 | 42 | | | 115-199 | |
| 0018 | 24 | | 1E | | 2-0 | 26-11-11 | | D01822 | 48 | | | D01598 | 10 | | | 001-099 | |
| 0018 | 22 | | 1E | | 0-5 | 26-11-11 | | D01822 | 17 | | | GD03130 | DC.. | E | *1 | 115-199 | |
| 0019 | 24 | | 1E | | 2-0 | 26-11-11 | | D01822 | 44 | | | D01598 | 6 | | | 001-099 | |
| 0019 | 24 | | 1E | | 2-0 | 26-11-11 | | D01822 | 15 | | | D01596 | 10 | | | 115-199 | |
| 0020 | 24 | | 1E | | 2-0 | 26-11-11 | | D01822 | 9 | | | D01598 | 14 | | | 001-099 | |
| 0020 | 24 | | 1E | | 2-0 | 26-11-11 | | D01822 | 55 | | | D01596 | 6 | | | 115-199 | |
| 0021 | 24 | | 1E | | 2-0 | 26-11-11 | | D01822 | 3 | | | D01598 | 16 | | | 001-099 | |
| 0021 | 24 | | 1E | | 2-0 | 26-11-11 | | D01822 | 39 | | | D01596 | 14 | | | 115-199 | |
| 0022 | 24 | | 1E | | 3-0 | 26-11-11 | | D01822 | 8 | | | TB0069Z | 2 | BJ | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1120 | 286N1120 | | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0022 | 24 | | 1E | | 2-0 | 26-11-11 | D01822 | | 45 | | | D01596 | | 16 | | 115-199 |
| 0023 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 1 | | | TB0069Z | | 1 | BJ | 001-099 |
| 0023 | 22 | | 1E | | 3-0 | 26-11-11 | D01596 | | 3 | | | GD01047 | DC.. | 2 | | 115-199 |
| 0024 | 24 | | 1E | | 0-3 | 26-11-11 | D01822 | | 13 | | | D01822 | | 42 | | 001-099 |
| 0024 | 22 | | 1E | | 3-0 | 26-11-11 | D01596 | | 18 | | | GD01047 | DC.. | 2 | | 115-199 |
| 0025 | 24 | | 1E | | 1-0 | 26-11-11 | D01822 | | 11 | | | SM00012 | | WI | | 001-099 |
| 0025 | 24 | | 1E | | 3-0 | 26-11-11 | D41944J | | 7 | | | SM00012 | | WI | | 115-199 |
| 0026 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 2 | | | TB0069Z | | 9 | BJ | 001-099 |
| 0026 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 11 | | | SM00012 | | WI | | 115-199 |
| 0027 | 22 | | 1E | | 0-5 | 26-11-11 | D01822 | | 17 | | | GD03130 | DC.. | E | *2 | 001-099 |
| 0027 | 24 | | 1E | | 3-0 | 26-11-11 | D41944J | | 37 | | | TB0069Z | | 9 | BJ | 115-199 |
| 0028 | 22 | | 1E | | 0-5 | 26-11-11 | D01822 | | 50 | | | GD03130 | DC.. | E | *2 | 001-099 |
| 0028 | 24 | | 1E | | 3-0 | 26-11-11 | D41946J | | 22 | | | TB0069Z | | 5 | BJ | 115-199 |
| 0029 | 22 | | 1E | | 0-3 | 26-11-11 | D01822 | | 49 | | | SM00054 | | WI | | 001-099 |
| 0029 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 7 | | | TB0069Z | | 5 | BJ | 115-199 |
| 0030 | 22 | | 1E | | 0-3 | 26-11-11 | D01822 | | 16 | | | SM00054 | | WI | | 001-099 |
| 0030 | 24 | | 1E | | 3-0 | 26-11-11 | D41946J | | 21 | | | TB0069Z | | 6 | BJ | 115-199 |
| 0031 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 36 | | | D41944J | | 2 | | 001-099 |
| 0031 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 10 | | | TB0069Z | | 6 | BJ | 115-199 |
| 0032 | 22 | | 1E | | 0-5 | 26-11-11 | D01822 | | 46 | | | GD03130 | DC.. | E | *1 | 001-099 |
| 0032 | 24 | | 1E | | 3-0 | 26-11-11 | D41944J | | 1 | | | TB0069Z | | 5 | BJ | 115-199 |
| 0033 | 22 | | 1E | | 0-5 | 26-11-11 | D01822 | | 14 | | | GD03130 | DC.. | E | *1 | 001-099 |
| 0033 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 36 | | | D41944J | | 2 | | 115-199 |
| 0034 | 24 | | 1E | | 3-0 | 26-11-11 | TB0069Y | A012 | BJ | | | D41944J | | 6 | | 001-099 |
| 0034 | 24 | | 1E | | 3-0 | 26-11-11 | D41944J | | 3 | | | SM00012 | | WI | | 115-199 |
| 0035 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 5 | | | D41936J | | 12 | | ALL |
| 0036 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 7 | | | TB0069Z | | 5 | BJ | 001-099 |
| 0036 | 24 | | 1E | | 3-0 | 26-11-11 | D41944J | | 5 | | | TB0069Z | | 2 | BJ | 115-199 |
| 0037 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 10 | | | TB0069Z | | 6 | BJ | 001-099 |
| 0037 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 8 | | | TB0069Z | | 2 | BJ | 115-199 |
| 0038 | 24 | | 1E | | 2-0 | 26-11-11 | D01822 | | 45 | | | D01596 | | 16 | | 001-099 |
| 0038 | 24 | | 1E | | 3-0 | 26-11-11 | D41944J | | 6 | | | TB0069Y | A007 | BJ | | 115-199 |
| 0039 | 24 | | 1E | | 2-0 | 26-11-11 | D01822 | | 39 | | | D01596 | | 14 | | 001-099 |
| 0039 | 24 | | 1E | | 3-0 | 26-11-11 | D01822 | | 47 | | | TB0069Y | A007 | BJ | | 115-199 |
| 0040 | 24 | | 1E | | 2-0 | 26-11-11 | D01822 | | 55 | | | D01596 | | 6 | | 001-099 |
| 0040 | 22 | | 1E | | 3-0 | 26-11-12 | D02110 | | 3 | | | GD01048 | DC.. | 2 | | 115-199 |
| 0041 | 24 | | 1E | | 2-0 | 26-11-11 | D01822 | | 15 | | | D01596 | | 10 | | 001-099 |
| 0041 | 24 | | 1E | | 2-0 | 26-11-12 | D02110 | | 10 | | | D01822 | | 19 | | 115-199 |
| 0042 | 24 | | 1E | | 3-0 | 26-11-11 | D41944J | | 8 | | | SM00012 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 2

Jan 21/2005



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



WIRE LIST
D280N032

91-21-11
Section W1120
Page 4
Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0084 | 22 | | 1E | | 3-0 | 26-11-21 | D01590 | | | 3 | GD02041 | DC.. | 2 | | 115-199 |
| 0085 | 24 | | 1E | | 3-0 | 26-11-12 | D41944J | | | 29 | TB0069Y | C011 | BJ | | 001-099 |
| 0085 | 22 | | 1E | | 3-0 | 26-11-21 | D01590 | | | 18 | GD02041 | DC.. | 2 | | 115-199 |
| 0086 | 24 | | 1E | | 3-0 | 26-11-21 | D41992J | | | 9 | D02330 | | 5 | | 115-199 |
| 0087 | 24 | | 1E | | 3-0 | 26-11-21 | D41992J | | | 8 | TB0069Z | | 14 | BJ | 115-199 |
| 0088 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | | 7 | TB0069Z | | 5 | BJ | 115-199 |
| 0089 | 24 | | 1E | | 3-0 | 26-11-21 | D41940J | | | 6 | TB0069Z | | 18 | BJ | 001-099 |
| 0089 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | | 8 | TB0069Z | | 2 | BJ | 115-199 |
| 0090 | 24 | | 1E | | 3-0 | 26-11-21 | D41946J | | | 42 | TB0069Z | | 13 | BJ | 001-099 |
| 0090 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | | 10 | TB0069Z | | 6 | BJ | 115-199 |
| 0091 | 24 | | 1E | | 3-0 | 26-11-21 | D01592 | | | 1 | TB0069Z | | 13 | BJ | 001-099 |
| 0091 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | | 11 | TB0069Z | | 14 | BJ | 115-199 |
| 0092 | 22 | | 1E | | 3-0 | 26-11-21 | D01592 | | | 3 | GD01048 | DC.. | 2 | | 001-099 |
| 0092 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | | 36 | D41946J | | 7 | | 115-199 |
| 0093 | 22 | | 1E | | 3-0 | 26-11-21 | D01592 | | | 18 | GD01048 | DC.. | 2 | | 001-099 |
| 0093 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | | 47 | TB0069Y | C007 | BJ | | 115-199 |
| 0094 | 24 | | 1E | | 3-0 | 26-11-21 | D01592 | | | 20 | D41946J | | 1 | | 001-099 |
| 0094 | 24 | | 1E | | 3-0 | 26-11-22 | D02330 | | | 22 | TB0069Y | C007 | BJ | | 115-199 |
| 0095 | 24 | | 1E | | 3-0 | 26-11-21 | D01592 | | | 19 | D41946J | | 13 | | 001-099 |
| 0095 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | | 18 | GD03132 | DC.. | E | *2 | 115-199 |
| 0096 | 24 | | 1E | | 3-0 | 26-11-21 | D01592 | | | 21 | D41946J | | 30 | | 001-099 |
| 0096 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | | 32 | GD03132 | DC.. | E | *3 | 115-199 |
| 0097 | 24 | | 1E | | 3-0 | 26-11-21 | D01590 | | | 1 | TB0069Z | | 18 | BJ | 001-099 |
| 0098 | 24 | | 1E | | 3-0 | 26-11-21 | D01590 | | | 20 | D41940J | | 15 | | 001-099 |
| 0098 | 22 | | 1E | | 3-0 | 26-11-22 | D02080 | | | 3 | GD02041 | DC.. | 2 | | 115-199 |
| 0099 | 24 | | 1E | | 3-0 | 26-11-21 | D01590 | | | 19 | D41940J | | 13 | | 001-099 |
| 0099 | 24 | | 1E | | 2-0 | 26-11-22 | D02080 | | | 10 | D02330 | | 19 | | 115-199 |
| 0100 | 24 | | 1E | | 3-0 | 26-11-21 | D01590 | | | 21 | D41940J | | 1 | | 001-099 |
| 0100 | 24 | | 1E | | 2-0 | 26-11-22 | D02080 | | | 6 | D02330 | | 54 | | 115-199 |
| 0101 | 22 | | 1E | | 3-0 | 26-11-21 | D01590 | | | 3 | GD02041 | DC.. | 2 | | 001-099 |
| 0101 | 24 | | 1E | | 2-0 | 26-11-22 | D02080 | | | 14 | D02330 | | 65 | | 115-199 |
| 0102 | 22 | | 1E | | 3-0 | 26-11-21 | D01590 | | | 18 | GD02041 | DC.. | 2 | | 001-099 |
| 0102 | 24 | | 1E | | 2-0 | 26-11-22 | D02080 | | | 16 | D02330 | | 28 | | 115-199 |
| 0103 | 24 | | 1E | | 3-0 | 26-11-22 | D41992J | | | 1 | D02330 | | 63 | | 115-199 |
| 0104 | 24 | | 1E | | 3-0 | 26-11-22 | D41946J | | | 14 | TB0069Y | A008 | BJ | | 115-199 |
| 0105 | 24 | | 1E | | 3-0 | 26-11-22 | D41946J | | | 12 | D02330 | | 62 | | 115-199 |
| 0106 | 24 | | 1E | | 2-0 | 26-11-21 | D02330 | | | 48 | D01592 | | 10 | | 001-099 |
| 0106 | 24 | | 1E | | 3-0 | 26-11-22 | D02330 | | | 33 | TB0069Z | | 18 | BJ | 115-199 |
| 0107 | 24 | | 1E | | 2-0 | 26-11-21 | D02330 | | | 44 | D01592 | | 6 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 5

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0107 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | 25 | | GD03132 | DC.. | E | *3 | 115-199 |
| 0108 | 24 | | 1E | | 2-0 | 26-11-21 | D02330 | | 9 | | D01592 | 14 | | | 001-099 |
| 0108 | 24 | | 1E | | 3-0 | 26-11-22 | D41946J | | 43 | | TB0069Y | A008 | BJ | | 115-199 |
| 0109 | 24 | | 1E | | 2-0 | 26-11-21 | D02330 | | 3 | | D01592 | 16 | | | 001-099 |
| 0109 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | 51 | | GD03132 | DC.. | E | *2 | 115-199 |
| 0110 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | 47 | | TB0069Y | C004 | BJ | | 001-099 |
| 0110 | 24 | | 1E | | 2-0 | 26-11-22 | D02330 | | 30 | | D02400 | 6 | | | 115-199 |
| 0111 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | 2 | | TB0069Z | 13 | BJ | | 001-099 |
| 0111 | 24 | | 1E | | 2-0 | 26-11-22 | D02330 | | 29 | | D02400 | 14 | | | 115-199 |
| 0112 | 22 | | 1E | | 0-3 | 26-11-21 | D02330 | | 49 | | SM00055 | | WI | | 001-099 |
| 0112 | 24 | | 1E | | 2-0 | 26-11-22 | D02330 | | 27 | | D02400 | 16 | | | 115-199 |
| 0113 | 22 | | 1E | | 0-3 | 26-11-21 | D02330 | | 16 | | SM00055 | | WI | | 001-099 |
| 0113 | 24 | | 1E | | 2-0 | 26-11-22 | D02330 | | 52 | | D02400 | 10 | | | 115-199 |
| 0114 | 22 | | 1E | | 0-5 | 26-11-21 | D02330 | | 50 | | GD03132 | DC.. | E | *2 | 001-099 |
| 0114 | 24 | | 1E | | 3-0 | 26-11-22 | D02330 | | 23 | | TB0069Y | A008 | BJ | | 115-199 |
| 0115 | 22 | | 1E | | 0-5 | 26-11-21 | D02330 | | 17 | | GD03132 | DC.. | E | *2 | 001-099 |
| 0115 | 22 | | 1E | | 3-0 | 26-11-22 | D02400 | | 3 | | GD01047 | DC.. | 2 | | 115-199 |
| 0116 | 22 | | 1E | | 0-5 | 26-11-21 | D02330 | | 46 | | GD03132 | DC.. | E | *1 | 001-099 |
| 0116 | 24 | | 1E | | 3-0 | 26-11-22 | D02330 | | 34 | | TB0069Z | 13 | BJ | | 115-199 |
| 0117 | 22 | | 1E | | 0-5 | 26-11-21 | D02330 | | 14 | | GD03132 | DC.. | E | *1 | 001-099 |
| 0117 | 24 | | 1E | | 3-0 | 26-12-11 | D04334 | | 64 | | TB0069Y | A012 | BJ | | 115-199 |
| 0118 | 24 | | 1E | | 0-3 | 26-11-21 | D02330 | | 13 | | D02330 | 42 | | | 001-099 |
| 0118 | 24 | | 1E | | 3-0 | 26-12-11 | D04334 | | 30 | | D41944J | 26 | | | 115-199 |
| 0119 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | 11 | | TB0069Z | 14 | BJ | | 001-099 |
| 0119 | 24 | | 1E | | 3-0 | 26-12-11 | D04334 | | 54 | | D41986J | 5 | | | 115-199 |
| 0120 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | 7 | | TB0069Z | 5 | BJ | | 001-099 |
| 0120 | 24 | | 1E | | 3-0 | 26-12-11 | D41986J | | 6 | | TB0069Y | A004 | BJ | | 115-199 |
| 0121 | 24 | | 1E | | 3-0 | 26-12-11 | D04334 | | 65 | | TB0069Y | A004 | BJ | | 115-199 |
| 0122 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | 10 | | TB0069Z | 6 | BJ | | 001-099 |
| 0123 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | 8 | | TB0069Z | 2 | BJ | | 001-099 |
| 0123 | 24 | | 1E | | 3-0 | 26-12-11 | D04334 | | 62 | | D41944J | 28 | | | 115-199 |
| 0124 | 24 | | 1E | | 3-0 | 26-11-21 | D02330 | | 1 | | TB0069Z | 18 | BJ | | 001-099 |
| 0124 | 24 | | 1E | | 3-0 | 26-12-11 | D04334 | | 31 | | TB0069Y | A004 | BJ | | 115-199 |
| 0125 | 24 | | 1E | | 2-0 | 26-11-21 | D02330 | | 45 | | D01590 | 16 | | | 001-099 |
| 0125 | 24 | | 1E | | 3-0 | 26-12-11 | D04334 | | 22 | | SM00011 | | WI | | 115-199 |
| 0126 | 24 | | 1E | | 2-0 | 26-11-21 | D02330 | | 39 | | D01590 | 14 | | | 001-099 |
| 0126 | 24 | | 1E | | 0-3 | 26-12-11 | D04334 | | 52 | | SM00017 | | WI | | 115-199 |
| 0127 | 24 | | 1E | | 2-0 | 26-11-21 | D02330 | | 55 | | D01590 | 6 | | | 001-099 |
| 0127 | 24 | | 1E | | 3-0 | 26-12-11 | D04334 | | 33 | | TB0069Z | 1 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 6

Jan 21/2005



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0150 | 24 | | 1E | | 3-0 | 26-11-22 | D02330 | | 63 | | D41992J | | 3 | | 001-099 |
| 0150 | 24 | | 1E | | 3-0 | 26-15-11 | D04078 | | 44 | | SM00041 | | | WI | 115-199 |
| 0151 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | 25 | | GD03132 | DC.. | E | *3 | 001-099 |
| 0151 | 24 | | 1E | | 2-0 | 26-15-11 | D04078 | | 9 | | D01918 | | 14 | | 115-199 |
| 0152 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | 51 | | GD03132 | DC.. | E | *2 | 001-099 |
| 0152 | 24 | | 1E | | 2-0 | 26-15-11 | D04078 | | 3 | | D01918 | | 16 | | 115-199 |
| 0153 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | 18 | | GD03132 | DC.. | E | *2 | 001-099 |
| 0153 | 22 | | 1E | | 3-0 | 26-15-11 | D01918 | | 3 | | GD01048 | DC.. | 2 | | 115-199 |
| 0154 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | 32 | | GD03132 | DC.. | E | *3 | 001-099 |
| 0154 | 22 | | 1E | | 3-0 | 26-15-11 | D01918 | | 18 | | GD01048 | DC.. | 2 | | 115-199 |
| 0155 | 24 | | 1E | | 0-3 | 26-11-22 | D02330 | | 60 | | D02330 | | 53 | | 001-099 |
| 0155 | 24 | | 1E | | 3-0 | 26-15-11 | D40946J | | 2 | | TB0069Z | | 10 | BJ | 115-199 |
| 0156 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | 20 | | GD03132 | DC.. | E | *3 | 001-099 |
| 0156 | 24 | | 1E | | 3-0 | 26-15-11 | D04078 | | 11 | | TB0069Z | | 10 | BJ | 115-199 |
| 0157 | 22 | | 1E | | 0-5 | 26-11-22 | D02330 | | 21 | | GD03132 | DC.. | E | *3 | 001-099 |
| 0157 | 24 | | 1E | | 3-0 | 26-15-11 | D40946J | | 1 | | TB0069Z | | 17 | BJ | 115-199 |
| 0158 | 24 | | 1E | | 3-0 | 26-11-22 | D02330 | | 22 | | TB0069Y | C004 | BJ | | 001-099 |
| 0158 | 24 | | 1E | | 3-0 | 26-15-11 | D41944J | | 21 | | TB0069Z | | 17 | BJ | 115-199 |
| 0159 | 24 | | 1E | | 3-0 | 26-11-22 | D02330 | | 33 | | TB0069Z | | 18 | BJ | 001-099 |
| 0159 | 24 | | 1E | | 3-0 | 26-15-11 | D41944J | | 42 | | TB0069Z | | 10 | BJ | 115-199 |
| 0160 | 24 | | 1E | | 2-0 | 26-11-22 | D02330 | | 28 | | D02080 | | 16 | | 001-099 |
| 0160 | 24 | | 1E | | 3-0 | 26-15-11 | D04078 | | 47 | | TB0069Y | C003 | BJ | | 115-199 |
| 0161 | 24 | | 1E | | 2-0 | 26-11-22 | D02330 | | 65 | | D02080 | | 14 | | 001-099 |
| 0161 | 24 | | 1E | | 3-0 | 26-15-11 | D04078 | | 36 | | D41986J | | 13 | | 115-199 |
| 0162 | 24 | | 1E | | 2-0 | 26-11-22 | D02330 | | 19 | | D02080 | | 10 | | 001-099 |
| 0162 | 24 | | 1E | | 3-0 | 26-15-11 | D41986J | | 15 | | TB0069Z | | 10 | BJ | 115-199 |
| 0163 | 24 | | 1E | | 2-0 | 26-11-22 | D02330 | | 54 | | D02080 | | 6 | | 001-099 |
| 0163 | 24 | | 1E | | 3-0 | 26-15-11 | D40946J | | 8 | | TB0069Y | C003 | BJ | | 115-199 |
| 0164 | 24 | | 1E | | 3-0 | 26-11-22 | D02080 | | 1 | | TB0069Z | | 18 | BJ | 001-099 |
| 0164 | 24 | | 1E | | 3-0 | 26-15-11 | D41986J | | 16 | | TB0069Y | A003 | BJ | | 115-199 |
| 0165 | 22 | | 1E | | 3-0 | 26-11-22 | D02080 | | 3 | | GD02041 | DC.. | 2 | | 001-099 |
| 0165 | 24 | | 1E | | 3-0 | 26-15-11 | D41986J | | 17 | | TB0069Y | C003 | BJ | | 115-199 |
| 0166 | 24 | | 1E | | 3-0 | 26-11-22 | D02080 | | 19 | | D41992J | | 2 | | 001-099 |
| 0166 | 24 | | 1E | | 3-0 | 26-15-11 | D04078 | | 8 | | TB0069Z | | 2 | BJ | 115-199 |
| 0167 | 24 | | 1E | | 3-0 | 26-11-22 | D02080 | | 20 | | D41992J | | 14 | | 001-099 |
| 0167 | 24 | | 1E | | 3-0 | 26-15-11 | D04078 | | 10 | | TB0069Z | | 6 | BJ | 115-199 |
| 0168 | 24 | | 1E | | 3-0 | 26-15-11 | D01918 | | 6 | | SM00041 | | | WI | 115-199 |
| 0169 | 24 | | 1E | | 3-0 | 26-11-22 | D41946J | | 43 | | TB0069Y | A008 | BJ | | 001-099 |
| 0169 | 24 | | 1E | | 3-0 | 26-15-11 | D01916 | | 6 | | SM00040 | | | WI | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 8

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1120 | 286N1120 | | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0170 | 24 | | 1E | | 3-0 | 26-11-22 | D41946J | | 14 | | TB0069Y | A008 | BJ | | 001-099 | |
| 0170 | 24 | | 1E | | 3-0 | 26-15-11 | D41986J | | 19 | | SM00040 | | WI | | 115-199 | |
| 0171 | 24 | | 1E | | 3-0 | 26-15-11 | D41986J | | 20 | | SM00041 | | WI | | 115-199 | |
| 0172 | 24 | | 1E | | 3-0 | 26-15-11 | D01916 | | 19 | | D40218J | 11 | | | 001-099 | |
| 0173 | 24 | | 1E | | 3-0 | 26-15-11 | D01916 | | 21 | | D40218J | 9 | | | 001-099 | |
| 0173 | 24 | | 1E | | 3-0 | 26-15-12 | D40946J | | 3 | | D41946J | 29 | | | 115-199 | |
| 0174 | 24 | | 1E | | 2-0 | 26-15-11 | D01916 | | 1 | | TB0069Z | 17 | BJ | | 001-099 | |
| 0174 | 24 | | 1E | | 3-0 | 26-15-12 | D40946J | | 4 | | D41946J | 27 | | | 115-199 | |
| 0175 | 22 | | 1E | | 2-0 | 26-15-11 | D01916 | | 3 | | GD01048 | DC.. | 2 | | 001-099 | |
| 0175 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 1 | | SM00001 | | WI | | 115-199 | |
| 0176 | 22 | | 1E | | 2-0 | 26-15-11 | D01916 | | 18 | | GD01048 | DC.. | 2 | | 001-099 | |
| 0176 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 33 | | SM00001 | | WI | | 115-199 | |
| 0177 | 24 | | 1E | | 2-0 | 26-15-11 | D01916 | | 10 | | D04078 | 15 | | | 001-099 | |
| 0177 | 24 | | 1E | | 2-0 | 26-16-11 | D41992J | | 15 | | SM00001 | | WI | | 115-199 | |
| 0178 | 24 | | 1E | | 2-0 | 26-15-11 | D01916 | | 6 | | D04078 | 55 | | | 001-099 | |
| 0178 | 24 | | 1E | | 3-0 | 26-16-11 | D40220J | | 10 | | SM00001 | | WI | | 115-199 | |
| 0179 | 24 | | 1E | | 2-0 | 26-15-11 | D01916 | | 14 | | D04078 | 39 | | | 001-099 | |
| 0179 | 24 | | 1E | | 3-0 | 26-16-11 | D40220J | | 11 | | D04254 | 39 | | | 115-199 | |
| 0180 | 24 | | 1E | | 2-0 | 26-15-11 | D01916 | | 16 | | D04078 | 45 | | | 001-099 | |
| 0180 | 24 | | 1E | | 3-0 | 26-16-11 | D40220J | | 12 | | D04254 | 55 | | | 115-199 | |
| 0181 | 24 | | 1E | | 3-0 | 26-15-11 | D04078 | | 1 | | TB0069Z | 17 | BJ | | 001-099 | |
| 0181 | 24 | | 1E | | 2-0 | 26-16-11 | D40218J | | 33 | | SM00001 | | WI | | 115-199 | |
| 0182 | 22 | | 1E | | 0-5 | 26-15-11 | D04078 | | 49 | | SM00019 | | WI | | 001-099 | |
| 0182 | 24 | | 1E | | 4-0 | 26-16-11 | D40218J | | 34 | | D04254 | 65 | | | 115-199 | |
| 0183 | 22 | | 1E | | 0-5 | 26-15-11 | D04078 | | 16 | | SM00019 | | WI | | 001-099 | |
| 0183 | 24 | | 1E | | 4-0 | 26-16-11 | D40218J | | 35 | | D04254 | 54 | | | 115-199 | |
| 0184 | 22 | | 1E | | 0-5 | 26-15-11 | D04078 | | 50 | | GD03134 | DC.. | E | *2 | 001-099 | |
| 0184 | 24 | | 1E | | 2-0 | 26-16-11 | D41944J | | 47 | | TB0069Y | A015 | BJ | | 115-199 | |
| 0185 | 24 | | 1E | | 2-0 | 26-15-11 | D04078 | | 47 | | TB0069Y | C003 | BJ | | 001-099 | |
| 0185 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 11 | | TB0069Y | A015 | BJ | | 115-199 | |
| 0186 | 24 | | 1E | | 2-0 | 26-15-11 | D04078 | | 11 | | TB0069Z | 10 | BJ | | 001-099 | |
| 0186 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 23 | | TB0069Y | C016 | BJ | | 115-199 | |
| 0187 | 24 | | 1E | | 2-0 | 26-15-11 | D04078 | | 2 | | TB0069Y | A003 | BJ | | 001-099 | |
| 0187 | 24 | | 1E | | 2-0 | 26-16-11 | D41946J | | 2 | | TB0069Y | C016 | BJ | | 115-199 | |
| 0188 | 24 | | 1E | | 2-0 | 26-15-11 | D04078 | | 48 | | D01918 | 10 | | | 001-099 | |
| 0188 | 24 | | 1E | | 2-0 | 26-16-11 | D40946J | | 9 | | SM00002 | | WI | | 115-199 | |
| 0189 | 24 | | 1E | | 2-0 | 26-15-11 | D04078 | | 44 | | D01918 | 6 | | | 001-099 | |
| 0189 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 47 | | SM00002 | | WI | | 115-199 | |
| 0190 | 24 | | 1E | | 2-0 | 26-15-11 | D04078 | | 9 | | D01918 | 14 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 9

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0190 | 24 | | 1E | | 3-0 | 26-16-11 | | D04254 | | 22 | | SM00002 | | WI | | 115-199 |
| 0191 | 24 | | 1E | | 2-0 | 26-15-11 | | D04078 | | 3 | | D01918 | 16 | | | 001-099 |
| 0191 | 20 | | 1E | | 2-0 | 26-23-11 | | D41944J | | 52 | | SM00004 | | WI | | 115-199 |
| 0192 | 24 | | 1E | | 2-0 | 26-15-11 | | D01918 | | 1 | | TB0069Y | A003 | BJ | | 001-099 |
| 0192 | 20 | | 1E | | 3-0 | 26-23-11 | | D40218J | | 44 | | SM00004 | | WI | | 115-199 |
| 0193 | 22 | | 1E | | 2-0 | 26-15-11 | | D01918 | | 3 | | GD02041 | DC.. | 2 | | 001-099 |
| 0193 | 20 | | 1E | | 3-0 | 26-23-11 | | D41944J | | 53 | | D40218J | 43 | | | 115-199 |
| 0194 | 22 | | 1E | | 2-0 | 26-15-11 | | D01918 | | 18 | | GD02041 | DC.. | 2 | | 001-099 |
| 0194 | 20 | | 1E | | 3-0 | 26-23-11 | | D41944J | | 54 | | D40220J | 20 | | | 115-199 |
| 0195 | 24 | | 1E | | 2-0 | 26-15-11 | | D41986J | | 9 | | TB0069Y | A003 | BJ | | 001-099 |
| 0195 | 22 | | 1E | | 2-0 | 26-23-11 | | D41944J | | 50 | | SM00004 | | WI | | 115-199 |
| 0196 | 24 | | 1E | | 3-0 | 26-15-11 | | D41992J | | 12 | | TB0069Z | 17 | BJ | | 001-099 |
| 0196 | 24 | | 1E | | 3-0 | 26-18-11 | | D41946J | | 44 | | D40218J | 1 | | | 115-199 |
| 0197 | 24 | | 1E | | 3-0 | 26-15-11 | | D40946J | | 1 | | TB0069Z | 17 | BJ | | 001-099 |
| 0197 | 24 | | 1E | | 3-0 | 26-18-11 | | D41946J | | 45 | | D40218J | 8 | | | 115-199 |
| 0198 | 24 | | 1E | | 3-0 | 26-15-11 | | D40946J | | 2 | | TB0069Z | 10 | BJ | | 001-099 |
| 0198 | 24 | | 1E | | 3-0 | 26-18-11 | | D41946J | | 46 | | D40218J | 22 | | | 115-199 |
| 0199 | 24 | | 1E | | 3-0 | 26-15-11 | | D40946J | | 8 | | TB0069Y | C003 | BJ | | 001-099 |
| 0199 | 24 | | 1E | | 3-0 | 26-18-11 | | D41946J | | 47 | | D40218J | 24 | | | 115-199 |
| 0200 | 24 | | 1E | | 2-0 | 26-15-11 | | D41986J | | 13 | | D04078 | 36 | | | 001-099 |
| 0200 | 24 | | 1E | | 3-0 | 26-18-11 | | D41946J | | 48 | | D40218J | 26 | | | 115-199 |
| 0201 | 24 | | 1E | | 3-0 | 26-15-11 | | D41944J | | 42 | | TB0069Z | 10 | BJ | | 001-099 |
| 0201 | 24 | | 1E | | 3-0 | 26-18-11 | | D41946J | | 49 | | D40218J | 28 | | | 115-199 |
| 0202 | 24 | | 1E | | 3-0 | 26-15-11 | | D41944J | | 41 | | D04078 | 5 | | | 001-099 |
| 0202 | 24 | | 1E | | 3-0 | 26-18-11 | | D41946J | | 50 | | D40218J | 30 | | | 115-199 |
| 0203 | 24 | | 1E | | 3-0 | 26-15-11 | | D01918 | | 19 | | D40220J | 3 | | | 001-099 |
| 0203 | 24 | | 1E | | 3-0 | 26-18-11 | | D41946J | | 51 | | D40218J | 32 | | | 115-199 |
| 0204 | 24 | | 1E | | 3-0 | 26-15-11 | | D01918 | | 21 | | D40220J | 1 | | | 001-099 |
| 0205 | 20 | | 1E | | 2-0 | 26-23-11 | | D41946J | | 32 | | SM00005 | | WI | | 115-199 |
| 0206 | 22 | | 1E | | 0-5 | 26-15-11 | | D04078 | | 17 | | GD03134 | DC.. | E | *2 | 001-099 |
| 0206 | 20 | | 1E | | 2-0 | 26-23-11 | | D40220J | | 19 | | SM00005 | | WI | | 115-199 |
| 0207 | 22 | | 1E | | 0-5 | 26-15-11 | | D04078 | | 46 | | GD03134 | DC.. | E | *1 | 001-099 |
| 0207 | 20 | | 1E | | 3-0 | 26-23-11 | | D41946J | | 33 | | D40220J | 21 | | | 115-199 |
| 0208 | 22 | | 1E | | 0-5 | 26-15-11 | | D04078 | | 14 | | GD03134 | DC.. | E | *1 | 001-099 |
| 0208 | 20 | | 1E | | 3-0 | 26-23-11 | | D41946J | | 34 | | D40218J | 45 | | | 115-199 |
| 0209 | 24 | | 1E | | 0-3 | 26-15-11 | | D04078 | | 13 | | D04078 | 42 | | | 001-099 |
| 0209 | 22 | | 1E | | 2-0 | 26-23-11 | | D41944J | | 51 | | SM00005 | | WI | | 115-199 |
| 0210 | 24 | | 1E | | 1-0 | 26-15-11 | | D04078 | | 8 | | TB0069Z | 2 | BJ | | 001-099 |
| 0210 | 24 | | 1E | | 2-0 | 26-13-11 | | D41944J | | 25 | | SM00026 | | WI | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 10

Jan 21/2005



WIRE LIST

D280N032

91-21-11

Section W1120

Page 11

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1120 | 286N1120 | | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | | |
| 0239 | 24 | | 1E | | 4-0 | 26-16-11 | D40220J | | | 12 | | D04254 | 55 | | | 001-099 | |
| 0239 | 24 | | 1E | | 0-3 | 26-12-11 | D04334 | | | 19 | | SM00017 | | WI | | 115-199 | |
| 0240 | 24 | | 1E | | 4-0 | 26-16-11 | D40218J | | | 33 | | SM00001 | | WI | | 001-099 | |
| 0240 | 20 | | 1E | | 3-0 | 26-21-11 | D40220J | | | 8 | | D41944J | 34 | | | 115-199 | |
| 0241 | 24 | | 1E | | 4-0 | 26-16-11 | D40218J | | | 34 | | D04254 | 65 | | | 001-099 | |
| 0241 | 20 | | 1E | | 3-0 | 26-21-11 | D40218J | | | 20 | | D41944J | 55 | | | 115-199 | |
| 0242 | 24 | | 1E | | 4-0 | 26-16-11 | D40218J | | | 35 | | D04254 | 54 | | | 001-099 | |
| 0242 | 22 | | 1E | | 3-0 | 26-21-11 | D40220J | | | 9 | | D41946J | 37 | | | 115-199 | |
| 0243 | 24 | | 1E | | 3-0 | 26-16-11 | D41944J | | | 47 | | TB0069Y | A015 | BJ | | 001-099 | |
| 0243 | 20 | | 1E | | 3-0 | 26-22-21 | D41944J | | | 48 | | D40946J | 7 | | | 115-199 | |
| 0244 | 24 | | 1E | | 3-0 | 26-16-11 | D41946J | | | 2 | | TB0069Y | C016 | BJ | | 001-099 | |
| 0244 | 20 | | 1E | | 3-0 | 26-22-21 | D40946J | | | 6 | | TB0069Y | A011 | BJ | | 115-199 | |
| 0245 | 24 | | 1E | | 3-0 | 26-16-11 | D40946J | | | 9 | | TB0069Y | C008 | BJ | | 001-099 | |
| 0245 | 24 | | 1E | | 0-3 | 26-12-21 | D04252 | | | 32 | | SM00018 | | WI | | 115-199 | |
| 0246 | 24 | | 1E | | 0-3 | 26-12-21 | D04252 | | | 58 | | SM00018 | | WI | | 115-199 | |
| 0247 | 22 | | 1E | | 0-5 | 26-12-21 | D04252 | | | 21 | | GD03140 | DC.. | E | *2 | 115-199 | |
| 0248 | 24 | | 1E | | 0-3 | 26-12-21 | D04252 | | | 19 | | SM00018 | | WI | | 115-199 | |
| 0249 | 24 | | 1E | | 1-0 | 26-16-11 | D04254 | | | 2 | | SM00003 | | WI | | 001-099 | |
| 0249 | 20 | | 1E | | 3-0 | 26-22-21 | D40218J | | | 17 | | TB0069Y | A011 | BJ | | 115-199 | |
| 0250 | 24 | | 1E | | 1-0 | 26-16-11 | D04254 | | | 34 | | SM00003 | | WI | | 001-099 | |
| 0250 | 20 | | 1E | | 3-0 | 26-22-21 | D41944J | | | 49 | | TB0069Y | A011 | BJ | | 115-199 | |
| 0251 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | | | 17 | | GD03136 | DC.. | E | *1 | 001-099 | |
| 0252 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | | | 25 | | GD03136 | DC.. | E | *2 | 001-099 | |
| 0252 | 24 | | 1E | | 0-3 | 26-12-21 | D04252 | | | 20 | | SM00051 | | WI | | 115-199 | |
| 0253 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | | | 49 | | GD03136 | DC.. | E | *1 | 001-099 | |
| 0254 | 22 | | 1E | | 3-0 | 28-25-21 | D40946J | | | 11 | | D40218J | 15 | | | ALL | |
| 0255 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | | | 16 | | GD03136 | DC.. | E | *1 | 001-099 | |
| 0255 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | | 6 | | SM00026 | | WI | | 115-199 | |
| 0256 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | | 50 | | SM00002 | | WI | | 001-099 | |
| 0256 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | | 3 | | SM00026 | | WI | | 115-199 | |
| 0257 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | | 4 | | SM00002 | | WI | | 001-099 | |
| 0257 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | | 44 | | SM00027 | | WI | | 115-199 | |
| 0258 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | | 15 | | SM00002 | | WI | | 001-099 | |
| 0258 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | | 43 | | SM00027 | | WI | | 115-199 | |
| 0259 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | | | 21 | | GD03136 | DC.. | E | *2 | 001-099 | |
| 0259 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | | 40 | | SM00028 | | WI | | 115-199 | |
| 0260 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | | 20 | | SM00006 | | WI | | 001-099 | |
| 0260 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | | 39 | | SM00028 | | WI | | 115-199 | |
| 0261 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | | 53 | | SM00006 | | WI | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 12

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1120 | 286N1120 | | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0261 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | 55 | | | SM00029 | | WI | | 115-199 |
| 0262 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | 38 | | | SM00006 | | WI | | 001-099 |
| 0262 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | 37 | | | SM00029 | | WI | | 115-199 |
| 0263 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | 48 | | | SM00002 | | WI | | 001-099 |
| 0263 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | 14 | | | SM00031 | | WI | | 115-199 |
| 0264 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | 57 | | | SM00004 | | WI | | 001-099 |
| 0264 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | 13 | | | SM00031 | | WI | | 115-199 |
| 0265 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 7 | | | TB0069Z | 5 | BJ | | 001-099 |
| 0265 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | 42 | | | SM00031 | | WI | | 115-199 |
| 0266 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 8 | | | TB0069Z | 2 | BJ | | 001-099 |
| 0266 | 22 | | 1E | | 0-5 | 26-13-11 | D04334 | | 17 | | | GD03138 | DC.. | E | *1 | 115-199 |
| 0267 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 24 | | | TB0069Z | 2 | BJ | | 001-099 |
| 0267 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | 5 | | | D41936J | 5 | | | 115-199 |
| 0268 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | | 10 | | | TB0069Z | 6 | BJ | | 001-099 |
| 0268 | 22 | | 1E | | 0-5 | 26-13-11 | D04334 | | 49 | | | GD03138 | DC.. | E | *1 | 115-199 |
| 0269 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | | 46 | | | GD03136 | DC.. | E | *1 | 001-099 |
| 0269 | 22 | | 1E | | 0-5 | 26-13-11 | D04334 | | 16 | | | GD03138 | DC.. | E | *1 | 115-199 |
| 0270 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | 14 | | | SM00004 | | WI | | 001-099 |
| 0270 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | 50 | | | SM00032 | | WI | | 115-199 |
| 0271 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | | 13 | | | SM00004 | | WI | | 001-099 |
| 0271 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | 15 | | | SM00032 | | WI | | 115-199 |
| 0272 | 22 | | 1E | | 3-0 | 31-51-21 | D41944J | | 32 | | | TB0069Y | A015 | BJ | | ALL |
| 0273 | 22 | | 1E | | 3-0 | 31-51-21 | D41944J | | 33 | | | SM00012 | | WI | | ALL |
| 0274 | 22 | | 1E | | 3-0 | 31-51-21 | D41992J | | 11 | | | TB0069Z | 14 | BJ | | ALL |
| 0275 | 22 | | 1E | | 3-0 | 31-51-21 | D41986J | | 12 | | | TB0069Z | 10 | BJ | | ALL |
| 0276 | 22 | | 1E | | 4-0 | 31-51-33 | D41986J | | 14 | | | D40946J | 16 | | | 001-099 |
| 0276 | 22 | | 1E | | 3-0 | 31-51-33 | D41986J | | 14 | | | D40946J | 16 | | | 115-199 |
| 0277 | 22 | | 1E | | 3-0 | 31-51-21 | D41992J | | 10 | | | TB0069Y | C016 | BJ | | ALL |
| 0278 | 24 | | 1E | | 4-0 | 26-16-11 | D41986J | | 24 | | | SM00003 | | WI | | 001-099 |
| 0278 | 22 | | 1E | | 3-0 | 26-22-21 | D41944J | | 17 | | | D40218J | 18 | | | 115-199 |
| 0279 | 24 | | 1E | | 4-0 | 26-16-11 | D40220J | | 13 | | | SM00003 | | WI | | 001-099 |
| 0280 | 24 | | 1E | | 4-0 | 26-16-11 | D40220J | | 14 | | | D04254 | 3 | | | 001-099 |
| 0280 | 22 | | 1E | | 3-0 | 26-21-11 | D41944J | | 35 | | | D40218J | 19 | | | 115-199 |
| 0281 | 24 | | 1E | | 4-0 | 26-16-11 | D40220J | | 15 | | | D04254 | 44 | | | 001-099 |
| 0281 | 20 | | 1E | | 2-0 | 26-15-12 | D41946J | | 38 | | | TB0069Y | A011 | BJ | | 115-199 |
| 0282 | 24 | | 1E | | 4-0 | 26-16-11 | D40218J | | 36 | | | SM00003 | | WI | | 001-099 |
| 0282 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | 48 | | | SM00032 | | WI | | 115-199 |
| 0283 | 24 | | 1E | | 4-0 | 26-16-11 | D40218J | | 37 | | | D04254 | 27 | | | 001-099 |
| 0283 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | 4 | | | SM00032 | | WI | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 13

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0284 | 24 | | 1E | | 4-0 | 26-16-11 | | D40218J | | 38 | | D04254 | | 30 | | 001-099 |
| 0284 | 24 | | 1E | | 2-0 | 26-12-11 | | D41944J | | 30 | | SM00011 | | | WI | 115-199 |
| 0285 | 24 | | 1E | | 3-0 | 26-16-11 | | D41944J | | 39 | | TB0069Y | C016 | BJ | | 001-099 |
| 0285 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | | 23 | | TB0069Y | C011 | BJ | | 115-199 |
| 0286 | 24 | | 1E | | 3-0 | 26-16-11 | | D41946J | | 16 | | TB0069Y | A015 | BJ | | 001-099 |
| 0286 | 24 | | 1E | | 3-0 | 26-12-11 | | D41944J | | 29 | | TB0069Y | C011 | BJ | | 115-199 |
| 0287 | 24 | | 1E | | 4-0 | 26-16-11 | | D41986J | | 18 | | D04254 | | 63 | | 001-099 |
| 0287 | 24 | | 1E | | 3-0 | 26-12-11 | | D41944J | | 27 | | TB0069Y | A012 | BJ | | 115-199 |
| 0288 | 24 | | 1E | | 4-0 | 26-16-11 | | D41946J | | 28 | | D04254 | | 62 | | 001-099 |
| 0288 | 22 | | 1E | | 0-5 | 26-12-21 | | D04252 | | 25 | | GD03140 | DC.. | E | *2 | 115-199 |
| 0289 | 24 | | 1E | | 4-0 | 26-16-11 | | D41992J | | 13 | | D04254 | | 5 | | 001-099 |
| 0289 | 22 | | 1E | | 0-5 | 26-12-21 | | D04252 | | 51 | | GD03140 | DC.. | E | *2 | 115-199 |
| 0290 | 24 | | 1E | | 4-0 | 26-16-11 | | D41944J | | 40 | | D04254 | | 36 | | 001-099 |
| 0290 | 22 | | 1E | | 0-5 | 26-12-21 | | D04252 | | 18 | | GD03140 | DC.. | E | *2 | 115-199 |
| 0291 | 22 | | 1E | | 0-5 | 26-16-11 | | D04254 | | 51 | | GD03136 | DC.. | E | *2 | 001-099 |
| 0291 | 24 | | 1E | | 3-0 | 26-12-21 | | D04252 | | 30 | | D41946J | | 17 | | 115-199 |
| 0292 | 22 | | 1E | | 0-5 | 26-16-11 | | D04254 | | 18 | | GD03136 | DC.. | E | *2 | 001-099 |
| 0292 | 24 | | 1E | | 3-0 | 26-12-21 | | D04252 | | 64 | | TB0069Y | C012 | BJ | | 115-199 |
| 0293 | 24 | | 1E | | 0-3 | 26-16-11 | | D04254 | | 32 | | SM00005 | | | WI | 001-099 |
| 0293 | 24 | | 1E | | 3-0 | 26-12-21 | | D41992J | | 7 | | TB0069Y | C008 | BJ | | 115-199 |
| 0294 | 24 | | 1E | | 0-3 | 26-16-11 | | D04254 | | 58 | | SM00005 | | | WI | 001-099 |
| 0294 | 24 | | 1E | | 3-0 | 26-12-21 | | D41946J | | 18 | | TB0069Y | C012 | BJ | | 115-199 |
| 0295 | 24 | | 1E | | 0-3 | 26-16-11 | | D04254 | | 19 | | SM00005 | | | WI | 001-099 |
| 0295 | 24 | | 1E | | 3-0 | 26-12-21 | | D04252 | | 65 | | TB0069Y | C008 | BJ | | 115-199 |
| 0296 | 24 | | 1E | | 0-3 | 26-16-11 | | D04254 | | 52 | | SM00005 | | | WI | 001-099 |
| 0296 | 24 | | 1E | | 3-0 | 26-15-11 | | D04078 | | 7 | | TB0069Z | | 5 | BJ | 115-199 |
| 0297 | 24 | | 1E | | 3-0 | 26-15-11 | | D04078 | | 2 | | TB0069Y | A003 | BJ | | 115-199 |
| 0298 | 24 | | 1E | | 3-0 | 26-15-11 | | D04078 | | 1 | | TB0069Z | | 17 | BJ | 115-199 |
| 0299 | 22 | | 1E | | 0-5 | 26-15-11 | | D04078 | | 4 | | SM00019 | | | WI | 001-099 |
| 0299 | 24 | | 1E | | 0-3 | 26-15-11 | | D04078 | | 4 | | SM00019 | | | WI | 115-199 |
| 0300 | 24 | | 1E | | 4-0 | 26-18-11 | | D41946J | | 44 | | D40218J | | 1 | | 001-099 |
| 0300 | 24 | | 1E | | 0-3 | 26-15-11 | | D04078 | | 49 | | SM00019 | | | WI | 115-199 |
| 0301 | 24 | | 1E | | 4-0 | 26-18-11 | | D41946J | | 45 | | D40218J | | 8 | | 001-099 |
| 0301 | 24 | | 1E | | 0-3 | 26-15-11 | | D04078 | | 16 | | SM00019 | | | WI | 115-199 |
| 0302 | 24 | | 1E | | 4-0 | 26-18-11 | | D41946J | | 46 | | D40218J | | 22 | | 001-099 |
| 0302 | 22 | | 1E | | 0-5 | 26-15-11 | | D04078 | | 50 | | GD03134 | DC.. | E | * | 115-199 |
| 0303 | 24 | | 1E | | 4-0 | 26-18-11 | | D41946J | | 47 | | D40218J | | 24 | | 001-099 |
| 0303 | 24 | | 1E | | 3-0 | 26-11-12 | | D01822 | | 62 | | D41986J | | 1 | | 115-199 |
| 0304 | 24 | | 1E | | 4-0 | 26-18-11 | | D41946J | | 48 | | D40218J | | 26 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 14

Jan 21/2005



WIRE LIST

91-21-11

Section W1120

Page 15

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0343 | 20 | | 1E | | 3-0 | 26-23-11 | D40218J | 45 | | | D41946J | 34 | | | 001-099 |
| 0343 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | 2 | | | SM00003 | | WI | | 115-199 |
| 0344 | 22 | | 1E | | 3-0 | 26-23-11 | D41944J | 50 | | | TB0069Y | C012 | BJ | | 001-099 |
| 0344 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | 34 | | | SM00003 | | WI | | 115-199 |
| 0345 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | 17 | | | GD03136 | DC.. | E | *1 | 115-199 |
| 0346 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | 25 | | | GD03136 | DC.. | E | *2 | 115-199 |
| 0347 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | 49 | | | GD03136 | DC.. | E | *1 | 115-199 |
| 0348 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | 16 | | | GD03136 | DC.. | E | *1 | 115-199 |
| 0349 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 50 | | | SM00021 | | WI | | 115-199 |
| 0350 | 20 | | 1E | | 3-0 | 26-23-11 | D41946J | 32 | | | TB0069Y | C015 | BJ | | 001-099 |
| 0350 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 4 | | | SM00021 | | WI | | 115-199 |
| 0351 | 20 | | 1E | | 3-0 | 26-23-11 | D40220J | 19 | | | TB0069Y | C015 | BJ | | 001-099 |
| 0351 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | 21 | | | GD03136 | DC.. | E | *2 | 115-199 |
| 0352 | 20 | | 1E | | 4-0 | 26-23-11 | D40220J | 21 | | | D41946J | 33 | | | 001-099 |
| 0352 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 20 | | | SM00052 | | WI | | 115-199 |
| 0353 | 20 | | 1E | | 4-0 | 26-23-11 | D40220J | 20 | | | D41944J | 54 | | | 001-099 |
| 0353 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 53 | | | SM00052 | | WI | | 115-199 |
| 0354 | 22 | | 1E | | 3-0 | 26-23-11 | D41944J | 51 | | | TB0069Y | C015 | BJ | | 001-099 |
| 0354 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 15 | | | SM00021 | | WI | | 115-199 |
| 0355 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 48 | | | SM00021 | | WI | | 115-199 |
| 0356 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | 7 | | | TB0069Z | 5 | BJ | | 115-199 |
| 0357 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | 8 | | | TB0069Z | 2 | BJ | | 115-199 |
| 0358 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | 24 | | | TB0069Z | 2 | BJ | | 115-199 |
| 0359 | 24 | | 1E | | 3-0 | 26-16-11 | D04254 | 10 | | | TB0069Z | 6 | BJ | | 115-199 |
| 0360 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | 46 | | | GD03136 | DC.. | E | *1 | 115-199 |
| 0361 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 14 | | | SM00053 | | WI | | 115-199 |
| 0362 | 24 | | 1E | | 0-3 | 26-16-11 | SM00053 | | WI | | D04254 | 13 | | | 115-199 |
| 0363 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | 51 | | | GD03136 | DC.. | E | *2 | 115-199 |
| 0364 | 22 | | 1E | | 0-5 | 26-16-11 | D04254 | 18 | | | GD03136 | DC.. | E | *2 | 115-199 |
| 0365 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 32 | | | SM00022 | | WI | | 115-199 |
| 0366 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 58 | | | SM00022 | | WI | | 115-199 |
| 0367 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 19 | | | SM00022 | | WI | | 115-199 |
| 0368 | 24 | | 1E | | 0-3 | 26-16-11 | D04254 | 52 | | | SM00022 | | WI | | 115-199 |
| 0369 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | 8 | | | TB0069Z | 2 | BJ | | ALL |
| 0370 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | 11 | | | SM00012 | | WI | | ALL |
| 0371 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | 7 | | | TB0069Z | 5 | BJ | | ALL |
| 0372 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | 10 | | | TB0069Z | 6 | BJ | | ALL |
| 0373 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | 47 | | | SM00011 | | WI | | ALL |
| 0374 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | 1 | | | TB0069Z | 1 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 16

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0375 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | | 2 | TB0069Z | 9 | BJ | | ALL |
| 0376 | 24 | | 1E | | 3-0 | 26-13-11 | D04334 | | | 36 | D41944J | 19 | | | ALL |
| 0378 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 6 | SM00033 | | WI | | ALL |
| 0379 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 3 | SM00033 | | WI | | ALL |
| 0380 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 44 | SM00034 | | WI | | ALL |
| 0381 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 43 | SM00034 | | WI | | ALL |
| 0382 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 40 | SM00035 | | WI | | ALL |
| 0383 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 39 | SM00035 | | WI | | ALL |
| 0384 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 55 | SM00036 | | WI | | ALL |
| 0385 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 37 | SM00036 | | WI | | ALL |
| 0386 | 24 | | 1E | | 0-3 | 26-13-21 | D04252 | | | 14 | SM00039 | | WI | | ALL |
| 0387 | 24 | | 1E | | 0-3 | 26-13-21 | D04252 | | | 13 | SM00039 | | WI | | ALL |
| 0388 | 24 | | 1E | | 0-3 | 26-13-21 | D04252 | | | 42 | SM00039 | | WI | | ALL |
| 0389 | 22 | | 1E | | 0-5 | 26-13-21 | D04252 | | | 17 | GD03140 | DC.. | E | *1 | ALL |
| 0390 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 5 | D41940J | 8 | | | ALL |
| 0391 | 22 | | 1E | | 0-5 | 26-13-21 | D04252 | | | 49 | GD03140 | DC.. | E | *1 | ALL |
| 0392 | 22 | | 1E | | 0-5 | 26-13-21 | D04252 | | | 16 | GD03140 | DC.. | E | *1 | ALL |
| 0393 | 24 | | 1E | | 0-3 | 26-13-21 | D04252 | | | 50 | SM00038 | | WI | | ALL |
| 0394 | 24 | | 1E | | 0-3 | 26-13-21 | D04252 | | | 15 | SM00038 | | WI | | ALL |
| 0395 | 24 | | 1E | | 0-3 | 26-13-21 | D04252 | | | 48 | SM00038 | | WI | | ALL |
| 0396 | 24 | | 1E | | 0-3 | 26-13-21 | D04252 | | | 4 | SM00038 | | WI | | ALL |
| 0397 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 7 | TB0069Z | 5 | BJ | | ALL |
| 0398 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 10 | TB0069Z | 6 | BJ | | ALL |
| 0399 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 11 | TB0069Z | 14 | BJ | | ALL |
| 0400 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 8 | TB0069Z | 2 | BJ | | ALL |
| 0401 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 47 | TB0069Y | C019 | BJ | | 001-099 |
| 0401 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 47 | TB0069Y | C004 | BJ | | 115-199 |
| 0402 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 1 | TB0069Z | 18 | BJ | | ALL |
| 0403 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 2 | TB0069Z | 13 | BJ | | ALL |
| 0404 | 24 | | 1E | | 3-0 | 26-13-21 | D04252 | | | 36 | D41946J | 52 | | | ALL |
| 0405 | 24 | | 1E | | 2-0 | 26-13-21 | D41946J | | | 41 | SM00033 | | WI | | ALL |
| 0406 | 24 | | 1E | | 2-0 | 26-13-21 | D41946J | | | 10 | SM00034 | | WI | | ALL |
| 0407 | 24 | | 1E | | 2-0 | 26-13-21 | D41940J | | | 3 | SM00035 | | WI | | ALL |
| 0408 | 24 | | 1E | | 2-0 | 26-13-21 | D41940J | | | 5 | SM00036 | | WI | | ALL |
| 0409 | 22 | | 1E | | 0-5 | 26-13-21 | D04252 | | | 46 | GD03140 | DC.. | E | *1 | ALL |
| 0454 | 20 | | 1E | | 4-0 | 28-22-21 | D40218J | | | 2 | D41944J | 15 | | | 001-099 |
| 0454 | 20 | | 1E | | 3-0 | 28-22-21 | D40218J | | | 2 | D41944J | 15 | | | 115-199 |
| 0455 | 20 | | 1E | | 4-0 | 28-22-21 | D40218J | | | 5 | D41944J | 13 | | | 001-099 |
| 0455 | 20 | | 1E | | 3-0 | 28-22-21 | D40218J | | | 5 | D41944J | 13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 17

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | | | | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | |
| 0456 | 20 | | 1E | | 4-0 | 28-22-21 | | D40218J | 25 | | | D41944J | 12 | | | 001-099 |
| 0456 | 20 | | 1E | | 3-0 | 28-22-21 | | D40218J | 25 | | | D41944J | 12 | | | 115-199 |
| 0457 | 20 | | 1E | | 4-0 | 28-22-21 | | D40220J | 23 | | | D41946J | 55 | | | 001-099 |
| 0457 | 20 | | 1E | | 3-0 | 28-22-21 | | D40220J | 23 | | | D41946J | 55 | | | 115-199 |
| 0458 | 20 | | 1E | | 4-0 | 28-22-21 | | D40220J | 18 | | | D41946J | 54 | | | 001-099 |
| 0458 | 20 | | 1E | | 3-0 | 28-22-21 | | D40220J | 18 | | | D41946J | 54 | | | 115-199 |
| 0459 | 20 | | 1E | | 4-0 | 28-22-21 | | D40220J | 16 | | | D41946J | 53 | | | 001-099 |
| 0459 | 20 | | 1E | | 3-0 | 28-22-21 | | D40220J | 16 | | | D41946J | 53 | | | 115-199 |
| 0470 | 24 | | 1E | | 0-3 | 26-12-11 | | D04334 | 53 | | | SM00050 | | WI | | ALL |
| 0471 | 24 | | 1E | | 0-3 | 26-12-21 | | D04252 | 53 | | | SM00051 | | WI | | ALL |
| 0472 | 24 | | 1E | | 0-3 | 26-16-11 | | D04254 | 38 | | | SM00052 | | WI | | 115-199 |
| 0473 | 24 | | 1E | | 0-3 | 26-16-11 | | D04254 | 57 | | | SM00053 | | WI | | 115-199 |
| 0474 | 20 | | 1E | | 4-0 | 28-25-11 | | D41986J | 8 | | | D40218J | 6 | | | ALL |
| 0475 | 22 | | 1E | | 0-3 | 26-11-11 | | D01822 | 4 | | | SM00054 | | WI | | 001-099 |
| 0475 | 24 | | 1E | | 3-0 | 26-11-11 | | D01598 | 1 | | | TB0069Z | 9 | BJ | | 115-199 |
| 0476 | 24 | | 1E | | 3-0 | 26-11-11 | | D01822 | 47 | | | TB0069Y | A012 | BJ | | 001-099 |
| 0476 | 24 | | 1E | | 3-0 | 26-11-11 | | D01596 | 1 | | | TB0069Z | 1 | BJ | | 115-199 |
| 0477 | 24 | | 1E | | 3-0 | 26-11-21 | | D41946J | 8 | | | TB0069Y | C004 | BJ | | 001-099 |
| 0477 | 24 | | 1E | | 3-0 | 26-11-11 | | D01598 | 19 | | | D41944J | 38 | | | 115-199 |
| 0478 | 22 | | 1E | | 0-3 | 26-11-21 | | D02330 | 4 | | | SM00055 | | WI | | 001-099 |
| 0478 | 24 | | 1E | | 3-0 | 26-11-11 | | D01598 | 20 | | | D41944J | 9 | | | 115-199 |
| 0479 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 22 | | | SM00011 | | WI | | 001-099 |
| 0479 | 24 | | 1E | | 3-0 | 26-11-11 | | D01598 | 21 | | | D41944J | 11 | | | 115-199 |
| 0480 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 23 | | | TB0069Y | C011 | BJ | | 001-099 |
| 0480 | 24 | | 1E | | 3-0 | 26-11-11 | | D01596 | 20 | | | D41936J | 13 | | | 115-199 |
| 0481 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 30 | | | D41944J | 26 | | | 001-099 |
| 0481 | 24 | | 1E | | 3-0 | 26-11-11 | | D01596 | 19 | | | D41936J | 10 | | | 115-199 |
| 0482 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 27 | | | TB0069Y | A020 | BJ | | 001-099 |
| 0482 | 24 | | 1E | | 3-0 | 26-11-11 | | D01596 | 21 | | | D41936J | 1 | | | 115-199 |
| 0483 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 64 | | | TB0069Y | A020 | BJ | | 001-099 |
| 0483 | 24 | | 1E | | 3-0 | 26-11-12 | | D02110 | 1 | | | TB0069Z | 1 | BJ | | 115-199 |
| 0484 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 62 | | | D41944J | 28 | | | 001-099 |
| 0484 | 24 | | 1E | | 3-0 | 26-11-21 | | D01592 | 1 | | | TB0069Z | 13 | BJ | | 115-199 |
| 0485 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 54 | | | D41986J | 5 | | | 001-099 |
| 0485 | 24 | | 1E | | 3-0 | 26-11-21 | | D01590 | 1 | | | TB0069Z | 18 | BJ | | 115-199 |
| 0486 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 65 | | | TB0069Y | A019 | BJ | | 001-099 |
| 0486 | 24 | | 1E | | 3-0 | 26-11-21 | | D01592 | 20 | | | D41946J | 1 | | | 115-199 |
| 0487 | 24 | | 1E | | 3-0 | 26-12-11 | | D04334 | 31 | | | TB0069Y | A019 | BJ | | 001-099 |
| 0487 | 24 | | 1E | | 3-0 | 26-11-21 | | D01592 | 19 | | | D41946J | 13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 18

Jan 21/2005



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



WIRE LIST
D280N032

91-21-11
Section W1120
Page 20
Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1120 | 286N1120 | P54-FIRE DETECTION, DUCT LEAK & OVERHEAT DET (continued) | | | | | | | | | | | | | |
| 0543 | 22 | | 1E | | 0-5 | 26-13-11 | D04334 | | | 49 | GD03138 | DC.. | E | *1 | 001-099 |
| 0544 | 22 | | 1E | | 0-5 | 26-13-11 | D04334 | | | 16 | GD03138 | DC.. | E | *1 | 001-099 |
| 0545 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | | 50 | SM00032 | | WI | | 001-099 |
| 0546 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | | 15 | SM00032 | | WI | | 001-099 |
| 0547 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | | 48 | SM00032 | | WI | | 001-099 |
| 0548 | 24 | | 1E | | 0-3 | 26-13-11 | D04334 | | | 4 | SM00032 | | WI | | 001-099 |
| 0549 | 24 | | 1E | | 2-0 | 26-13-11 | D41944J | | | 25 | SM00026 | | WI | | 001-099 |
| 0550 | 24 | | 1E | | 2-0 | 26-13-11 | D41944J | | | 14 | SM00027 | | WI | | 001-099 |
| 0551 | 24 | | 1E | | 2-0 | 26-13-11 | D41936J | | | 3 | SM00028 | | WI | | 001-099 |
| 0552 | 24 | | 1E | | 2-0 | 26-13-11 | D41936J | | | 7 | SM00029 | | WI | | 001-099 |
| PA01 | | | | | 0-0 | 26-11-21 | D01590 | | | 2 | D01590 | | | 5 | ALL |
| PB01 | | | | | 0-0 | 26-11-21 | D01592 | | | 2 | D01592 | | | 5 | ALL |
| PC01 | | | | | 0-0 | 26-11-11 | D01596 | | | 2 | D01596 | | | 5 | ALL |
| PD01 | | | | | 0-0 | 26-11-11 | D01598 | | | 2 | D01598 | | | 5 | ALL |
| PE01 | | | | | 0-0 | 26-11-11 | D01822 | | | 35 | D01822 | | | 66 | ALL |
| PF01 | | | | | 0-0 | 26-15-11 | D01916 | | | 2 | D01916 | | | 5 | ALL |
| PG01 | | | | | 0-0 | 26-15-11 | D01918 | | | 2 | D01918 | | | 5 | ALL |
| PH01 | | | | | 0-0 | 26-11-22 | D02080 | | | 2 | D02080 | | | 5 | ALL |
| PI01 | | | | | 0-0 | 26-11-12 | D02110 | | | 2 | D02110 | | | 5 | ALL |
| PJ01 | | | | | 0-0 | 26-11-21 | D02330 | | | 35 | D02330 | | | 66 | ALL |
| PK01 | | | | | 0-0 | 26-11-12 | D02362 | | | 2 | D02362 | | | 5 | ALL |
| PL01 | | | | | 0-0 | 26-11-22 | D02400 | | | 2 | D02400 | | | 5 | ALL |
| PM01 | | | | | 0-0 | 26-15-11 | D04078 | | | 35 | D04078 | | | 66 | ALL |
| PN01 | | | | | 0-0 | 26-12-21 | D04252 | | | 12 | D04252 | | | 56 | ALL |
| PO01 | | | | | 0-0 | 26-16-11 | D04254 | | | 35 | D04254 | | | 66 | ALL |
| PP01 | | | | | 0-0 | 26-12-11 | D04334 | | | 12 | D04334 | | | 56 | ALL |
| W1128 | 286N1128 | P34 MODULE WIRING | | | | | | | | | | | | | |
| 0001 | 12 | | HA | | 5-3 | 24-54-61 | T00103 | + | C | * | TB5034 | 3 | E | | 001-099 |
| 0001 | 12 | | HA | | 3-11 | 24-54-61 | T00103 | + | C | * | TB5034 | 3 | E | | 115-199 |
| 0002 | 20 | | GA | | 5-0 | 24-51-51 | K00102 | X1 | C | * | D40400J | 2 | | | 001-099 |
| 0003 | 20 | | GA | | 5-0 | 24-51-51 | K00102 | X2 | C | | GD01583 | DC.. | 2 | | 001-099 |
| 0004 | 18 | | GA | | 4-0 | 24-21-41 | C00905 | L3 | H | * | L00010 | 1 | C | | 001-099 |
| 0004 | 18 | | GA | | 3-11 | 24-21-41 | C00905 | L3 | H | * | L00010 | 1 | C | | 115-199 |
| 0005 | 18 | | GA | | 5-0 | 24-21-41 | L00010 | 2 | C | | GD01582 | AC.. | 2 | | 001-099 |
| 0005 | 18 | | GA | | 4-7 | 24-21-41 | L00010 | 2 | C | | GD01582 | AC.. | 2 | | 115-199 |
| 0006 | 18 | | GA | | 4-0 | 24-21-51 | K00114 | C2 | H | | L00009 | 1 | C | | 001-099 |
| 0006 | 18 | | GA | | 3-7 | 24-21-51 | K00114 | C2 | H | | L00009 | 1 | C | | 115-199 |
| 0007 | 18 | | GA | | 5-0 | 24-21-51 | L00009 | 2 | C | | GD01582 | AC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 21

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--------------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1128 | 286N1128 | | | P34 MODULE WIRING (continued) | | | | | | | | | | | |
| 0007 | 18 | | GA | | 4-8 | 24-21-51 | L00009 | | 2 | C | GD01582 | AC.. | 2 | | 115-199 |
| 0008 | 24 | | GK | | 6-0 | 24-22-12 | D01732 | | 21 | | TB0134Y | A001 | BJ | | 001-099 |
| 0008 | 24 | | GK | | 5-4 | 24-22-12 | D01732 | | 21 | | TB0134Y | A001 | BJ | | 115-199 |
| 0009 | 20 | | GA | | 5-0 | 24-22-12 | D01732 | | 14 | | D01734 | | 13 | | 001-099 |
| 0009 | 20 | | GA | | 4-11 | 24-22-12 | D01732 | | 14 | | D01734 | | 13 | | 115-199 |
| 0010 | 20 | | GA | | 5-0 | 24-22-22 | D01732 | | 18 | | D01734 | | 17 | | 001-099 |
| 0010 | 20 | | GA | | 4-11 | 24-22-22 | D01732 | | 18 | | D01734 | | 17 | | 115-199 |
| 0011 | 20 | | GA | | 7-0 | 24-22-41 | D01732 | | 4 | | GD01583 | DC.. | 2 | | 001-099 |
| 0011 | 20 | | GA | | 6-2 | 24-22-41 | D01732 | | 4 | | GD01583 | DC.. | 2 | | 115-199 |
| 0012 | 20 | | GA | | 7-0 | 24-22-41 | D01732 | | 40 | | GD01583 | DC.. | 2 | | 001-099 |
| 0012 | 20 | | GA | | 6-2 | 24-22-41 | D01732 | | 40 | | GD01583 | DC.. | 2 | | 115-199 |
| 0013 | 20 | | GA | | 6-0 | 24-22-41 | D01732 | | 37 | | TB0134A | C003 | 2 | | 001-099 |
| 0013 | 20 | | GA | | 5-4 | 24-22-41 | D01732 | | 37 | | TB0134A | C003 | 2 | | 115-199 |
| 0014 | 24 | | GK | | 5-0 | 24-27-11 | D01732 | | 2 | | D01734 | | 5 | | 001-099 |
| 0014 | 24 | | GK | | 4-11 | 24-27-11 | D01732 | | 2 | | D01734 | | 5 | | 115-199 |
| 0015 | 20 | | GA | | 5-0 | 24-27-11 | D01734 | | 6 | | GD01583 | DC.. | 2 | | 001-099 |
| 0015 | 20 | | GA | | 4-8 | 24-27-11 | D01734 | | 6 | | GD01583 | DC.. | 2 | | 115-199 |
| 0016 | 24 | | GK | | 5-0 | 24-27-21 | D01734 | | 9 | | D01732 | | 6 | | 001-099 |
| 0016 | 24 | | GK | | 4-11 | 24-27-21 | D01734 | | 9 | | D01732 | | 6 | | 115-199 |
| 0017 | 20 | | GA | | 5-0 | 24-27-21 | D01734 | | 10 | | GD01583 | DC.. | 2 | | 001-099 |
| 0017 | 20 | | GA | | 4-8 | 24-27-21 | D01734 | | 10 | | GD01583 | DC.. | 2 | | 115-199 |
| 0018 | 24 | | GK | | 6-0 | 24-27-41 | D01732 | | 10 | | TB0134Y | C001 | BJ | | 001-099 |
| 0018 | 24 | | GK | | 5-4 | 24-27-41 | D01732 | | 10 | | TB0134Y | C001 | BJ | | 115-199 |
| 0019 | 24 | | GK | | 5-0 | 24-27-41 | D01734 | | 26 | | TB0134Y | C001 | BJ | | 001-099 |
| 0019 | 24 | | GK | | 4-5 | 24-27-41 | D01734 | | 26 | | TB0134Y | C001 | BJ | | 115-199 |
| 0020 | 24 | | GK | | 5-0 | 24-41-11 | D01734 | | 22 | | TB0134B | A004 | 2 | | 001-099 |
| 0020 | 24 | | GK | | 4-5 | 24-41-11 | D01734 | | 22 | | TB0134B | A004 | 2 | | 115-199 |
| 0021 | 18 | | GA | | 4-0 | 24-41-11 | K00114 | | A1 | H | L00015 | | 1 | I | 001-099 |
| 0021 | 18 | | GA | | 3-10 | 24-41-11 | K00114 | | A1 | H | L00015 | | 1 | I | 115-199 |
| 0022 | 18 | | GA | | 5-0 | 24-41-11 | L00015 | | 2 | I | GD01582 | AC.. | 2 | | 001-099 |
| 0022 | 18 | | GA | | 4-8 | 24-41-11 | L00015 | | 2 | I | GD01582 | AC.. | 2 | | 115-199 |
| 0023 | 24 | | GK | | 5-0 | 24-41-11 | D01734 | | 21 | | D01732 | | 22 | | 001-099 |
| 0023 | 24 | | GK | | 4-11 | 24-41-11 | D01734 | | 21 | | D01732 | | 22 | | 115-199 |
| 0024 | 20 | | GA | | 5-0 | 24-41-11 | D01734 | | 41 | | GD01583 | DC.. | 2 | | 001-099 |
| 0024 | 20 | | GA | | 4-8 | 24-41-11 | D01734 | | 41 | | GD01583 | DC.. | 2 | | 115-199 |
| 0025 | 20 | | GA | | 5-0 | 24-41-11 | D01734 | | 8 | | GD01583 | DC.. | 2 | | 001-099 |
| 0025 | 20 | | GA | | 4-8 | 24-41-11 | D01734 | | 8 | | GD01583 | DC.. | 2 | | 115-199 |
| 0026 | 20 | | GA | | 7-0 | 24-41-11 | D01732 | | 8 | | GD01583 | DC.. | 2 | | 001-099 |
| 0026 | 20 | | GA | | 6-2 | 24-41-11 | D01732 | | 8 | | GD01583 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 22

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1128 | 286N1128 | | | P34 MODULE WIRING (continued) | | | | | | | | | | | |
| 0027 | 24 | | GK | | 5-0 | 24-41-12 | D01734 | | 1 | | GD01583 | DC.. | 2 | | 001-099 |
| 0027 | 20 | | GA | | 4-8 | 24-41-12 | D01734 | | 1 | | GD01583 | DC.. | 2 | | 115-199 |
| 0028 | 24 | | GK | | 5-0 | 24-41-12 | D01734 | | 4 | | GD01583 | DC.. | 2 | | 001-099 |
| 0028 | 20 | | GA | | 4-8 | 24-41-12 | D01734 | | 4 | | GD01583 | DC.. | 2 | | 115-199 |
| 0029 | 20 | | GA | | 5-0 | 24-51-51 | K00103 | | X2 | C | GD01583 | DC.. | 2 | | 001-099 |
| 0029 | 20 | | GA | | 5-5 | 24-51-51 | K00103 | | X2 | C | GD01583 | DC.. | 2 | | 115-199 |
| 0030 | 20 | | GA | | 5-0 | 24-51-61 | K00101 | | X2 | C | GD01583 | DC.. | 2 | | 001-099 |
| 0030 | 20 | | GA | | 5-5 | 24-51-61 | K00101 | | X2 | C | GD01583 | DC.. | 2 | | 115-199 |
| 0031 | 20 | | GA | | 5-0 | 24-51-61 | K00101 | | Y2 | C | D40400J | | 44 | | 001-099 |
| 0031 | 20 | | GA | | 4-11 | 24-51-61 | K00101 | | Y2 | C | D40400J | | 44 | | 115-199 |
| 0032 | 22 | | GA | | 8-0 | 24-54-61 | T00103 | | A | C | C00304 | A2 | D | | 001-099 |
| 0032 | 22 | | GA | | 7-3 | 24-54-61 | T00103 | | A | C | C00304 | A2 | D | | 115-199 |
| 0033 | 22 | | GA | | 8-0 | 24-54-61 | T00103 | | B | C | C00304 | B2 | D | | 001-099 |
| 0033 | 22 | | GA | | 7-3 | 24-54-61 | T00103 | | B | C | C00304 | B2 | D | | 115-199 |
| 0034 | 22 | | GA | | 8-0 | 24-54-61 | T00103 | | C | C | C00304 | C2 | D | | 001-099 |
| 0034 | 22 | | GA | | 7-4 | 24-54-61 | T00103 | | C | C | C00304 | C2 | D | | 115-199 |
| 0035 | 12 | | GA | | 7-2 | 24-54-61 | T00103 | | + | C | C01356 | =B | D | | 001-099 |
| 0035 | 12 | | GA | | 7-9 | 24-54-61 | T00103 | | + | C | C01356 | =B | D | | 115-199 |
| 0036 | 12 | | GA | | 8-8 | 24-54-61 | T00103 | | - | C | GD00743 | DC.. | E | | 001-099 |
| 0036 | 12 | | GA | | 8-4 | 24-54-61 | T00103 | | - | C | GD00743 | DC.. | E | | 115-199 |
| 0037 | 16 | | GA | | 8-0 | 24-41-11 | C00320 | | A1 | D | K00114 | A1 | H | * | 001-099 |
| 0037 | 16 | | GA | | 6-11 | 24-41-11 | C00320 | | A1 | D | K00114 | A1 | H | * | 115-199 |
| 0038 | 16 | | GA | | 8-0 | 24-41-11 | C00320 | | B1 | D | K00114 | B1 | H | | 001-099 |
| 0038 | 16 | | GA | | 7-0 | 24-41-11 | C00320 | | B1 | D | K00114 | B1 | H | | 115-199 |
| 0039 | 16 | | GA | | 8-0 | 24-41-11 | C00320 | | C1 | D | K00114 | C1 | H | | 001-099 |
| 0039 | 16 | | GA | | 7-0 | 24-41-11 | C00320 | | C1 | D | K00114 | C1 | H | | 115-199 |
| 0042 | 20 | | GA | | 5-0 | 25-31-11 | D41472J | | 53 | | D40956J | 21 | | | 001-099 |
| 0101 | 18 | | GA | | 6-0 | 24-21-41 | C00905 | | L3 | H | D41326J | 23 | 18 | | 001-099 |
| 0101 | 18 | | GA | | 5-0 | 24-21-41 | C00905 | | L3 | H | D41326J | 23 | 18 | | 115-199 |
| 0102 | 18 | | GA | | 7-0 | 24-21-41 | C00905 | | L2 | H | D41326J | 15 | 18 | | 001-099 |
| 0102 | 18 | | GA | | 5-0 | 24-21-41 | C00905 | | L2 | H | D41326J | 15 | 18 | | 115-199 |
| 0103 | 18 | | GA | | 7-0 | 24-21-41 | C00905 | | L1 | H | D41326J | 22 | 18 | | 001-099 |
| 0103 | 18 | | GA | | 5-0 | 24-21-41 | C00905 | | L1 | H | D41326J | 22 | 18 | | 115-199 |
| 0104 | 24 | | GK | | 2-0 | 24-22-12 | TB0134Y | | A001 | BJ | D40956J | 7 | | | 001-099 |
| 0104 | 24 | | GK | | 1-10 | 24-22-12 | TB0134Y | | A001 | BJ | D40956J | 7 | | | 115-199 |
| 0105 | 24 | | GK | | 2-0 | 24-22-12 | TB0134Y | | A001 | BJ | D40956J | 6 | | | 001-099 |
| 0105 | 24 | | GK | | 1-10 | 24-22-12 | TB0134Y | | A001 | BJ | D40956J | 6 | | | 115-199 |
| 0106 | 20 | | GA | | 6-0 | 24-22-12 | D01732 | | 13 | | D40956J | 5 | | | ALL |
| 0107 | 20 | | GA | | 5-0 | 24-22-12 | D01734 | | 14 | | D40956J | 8 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 23

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1128 | 286N1128 | | | P34 MODULE WIRING (continued) | | | | | | | | | | | |
| 0107 | 20 | | GA | | 4-6 | 24-22-12 | D01734 | 14 | | | D40956J | 8 | | | 115-199 |
| 0108 | 24 | | GK | | 5-0 | 24-22-22 | D01734 | 18 | | | D40956J | 25 | | | 001-099 |
| 0108 | 24 | | GK | | 4-6 | 24-22-22 | D01734 | 18 | | | D40956J | 25 | | | 115-199 |
| 0109 | 24 | | GK | | 6-0 | 24-22-22 | D01732 | 17 | | | D40956J | 1 | | | ALL |
| 0110 | 18 | | GA | | 6-0 | 24-22-41 | C00905 | T2 | H | | D41326J | 27 | 18 | | 001-099 |
| 0110 | 18 | | GA | | 4-6 | 24-22-41 | C00905 | T2 | H | | D41326J | 27 | 18 | | 115-199 |
| 0111 | 24 | | GK | | 6-0 | 24-22-41 | D01732 | 3 | | | D40400J | 7 | | | 001-099 |
| 0111 | 24 | | GK | | 5-2 | 24-22-41 | D01732 | 3 | | | D40400J | 7 | | | 115-199 |
| 0112 | 20 | | GA | | 6-0 | 24-22-41 | D01732 | 39 | | | D40400J | 6 | | | 001-099 |
| 0112 | 20 | | GA | | 5-2 | 24-22-41 | D01732 | 39 | | | D40400J | 6 | | | 115-199 |
| 0113 | 20 | | GA | | 6-0 | 24-22-41 | D01732 | 41 | | | D40400J | 5 | | | 001-099 |
| 0113 | 20 | | GA | | 5-2 | 24-22-41 | D01732 | 41 | | | D40400J | 5 | | | 115-199 |
| 0114 | 20 | | GA | | 3-0 | 24-22-41 | TB0134A | A003 | 2 | | D41326J | 29 | | | 001-099 |
| 0114 | 20 | | GA | | 2-0 | 24-22-41 | TB0134A | A003 | 2 | | D41326J | 29 | | | 115-199 |
| 0115 | 24 | | GK | | 2-0 | 24-22-41 | TB0134A | A003 | 2 | | D40400J | 52 | | | 001-099 |
| 0115 | 24 | | GK | | 1-7 | 24-22-41 | TB0134A | A003 | 2 | | D40400J | 52 | | | 115-199 |
| 0116 | 24 | | GK | | 6-0 | 24-27-11 | D01732 | 1 | | | D40956J | 2 | | | ALL |
| 0117 | 24 | | GK | | 6-0 | 24-27-21 | D01732 | 5 | | | D40956J | 4 | | | ALL |
| 0118 | 24 | | GK | | 7-0 | 24-27-41 | D01732 | 9 | | | D41326J | 31 | | | 001-099 |
| 0118 | 24 | | GK | | 6-2 | 24-27-41 | D01732 | 9 | | | D41326J | 31 | | | 115-199 |
| 0119 | 24 | | GK | | 5-0 | 24-27-41 | D01734 | 25 | | | D40400J | 47 | | | 001-099 |
| 0119 | 24 | | GK | | 4-2 | 24-27-41 | D01734 | 25 | | | D40400J | 47 | | | 115-199 |
| 0120 | 24 | | GK | | 2-0 | 24-27-41 | TB0134Y | C001 | BJ | | D40400J | 13 | | | 001-099 |
| 0120 | 24 | | GK | | 1-7 | 24-27-41 | TB0134Y | C001 | BJ | | D40400J | 13 | | | 115-199 |
| 0121 | 24 | | GK | | 2-0 | 24-41-11 | TB0134B | C004 | 2 | | D40400J | 38 | | | 001-099 |
| 0121 | 20 | | GA | | 1-7 | 24-41-11 | TB0134B | C004 | 2 | | D40400J | 38 | | | 115-199 |
| 0122 | 24 | | GK | | 3-0 | 24-41-11 | TB0134B | A004 | 2 | | D41326J | 30 | | | 001-099 |
| 0122 | 24 | | GK | | 2-0 | 24-41-11 | TB0134B | A004 | 2 | | D41326J | 30 | | | 115-199 |
| 0123 | 22 | | GA | | 4-0 | 24-41-11 | B00129 | = 1 | \$ | | D40400J | 35 | | | 001-099 |
| 0123 | 22 | | GA | | 3-9 | 24-41-11 | B00129 | = 1 | \$ | | D40400J | 35 | | | 115-199 |
| 0124 | 22 | | GA | | 4-0 | 24-41-11 | B00130 | = 1 | \$ | | D40400J | 36 | | | 001-099 |
| 0124 | 22 | | GA | | 3-9 | 24-41-11 | B00130 | = 1 | \$ | | D40400J | 36 | | | 115-199 |
| 0125 | 22 | | GA | | 5-0 | 24-41-11 | B00130 | = 2 | \$ | | D40378J | 2 | | | 001-099 |
| 0125 | 22 | | GA | | 4-4 | 24-41-11 | B00130 | = 2 | \$ | | D40378J | 2 | | | 115-199 |
| 0126 | 22 | | GA | | 5-0 | 24-41-11 | B00129 | = 2 | \$ | | D40378J | 1 | | | 001-099 |
| 0126 | 22 | | GA | | 4-4 | 24-41-11 | B00129 | = 2 | \$ | | D40378J | 1 | | | 115-199 |
| 0127 | 24 | | GK | | 5-0 | 24-41-11 | D01734 | 7 | | | D40400J | 37 | | | 001-099 |
| 0127 | 24 | | GK | | 4-2 | 24-41-11 | D01734 | 7 | | | D40400J | 37 | | | 115-199 |
| 0128 | 20 | | GA | | 5-0 | 24-41-11 | D01734 | 40 | | | D40400J | 39 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 24

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|-------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1128 | 286N1128 | | | P34 MODULE WIRING (continued) | | | | | | | | | | | | |
| 0128 | 20 | GA | | 4-2 | 24-41-11 | D01734 | 40 | | | | D40400J | 39 | | | 115-199 | |
| 0129 | 24 | GK | | 6-0 | 24-41-11 | D01732 | 7 | | | | D40400J | 31 | | | 001-099 | |
| 0129 | 24 | GK | | 5-2 | 24-41-11 | D01732 | 7 | | | | D40400J | 31 | | | 115-199 | |
| 0130 | 24 | GK | | 5-0 | 24-41-12 | D01734 | 2 | | | | K00102 | 12 | C | | 001-099 | |
| 0130 | 24 | GK | | 4-2 | 24-41-12 | D01734 | 2 | | | | D40400J | 51 | | | 115-199 | |
| 0131 | 24 | GK | | 11-0 | 24-41-12 | D01734 | 3 | | | | TB0047X | C005 | BJ | | 001-099 | |
| 0131 | 24 | GK | | 7-0 | 24-41-12 | D01734 | 3 | | | | TB0047X | C021 | BJ | | 115-199 | |
| 0132 | 24 | GK | | 2-0 | 24-41-12 | D40378J | 3 | | | | D40400J | 46 | | | 001-099 | |
| 0132 | 22 | GA | | 1-11 | 24-41-12 | D40378J | 3 | | | | D40400J | 46 | | | 115-199 | |
| 0133 | 24 | GK | | 6-0 | 24-41-12 | D40378J | 4 | | | | K00102 | 13 | C | | 001-099 | |
| 0133 | 22 | GA | | 1-11 | 24-41-12 | D40378J | 4 | | | | D40400J | 50 | | | 115-199 | |
| 0134 | 20 | GA | | 5-0 | 24-51-51 | K00103 | X1 | C | | | D40400J | 40 | | | 001-099 | |
| 0134 | 20 | GA | | 4-11 | 24-51-51 | K00103 | X1 | C | | | D40400J | 40 | | | 115-199 | |
| 0135 | 20 | GA | | 5-0 | 24-51-61 | K00101 | X1 | C | | | D40400J | 41 | | | 001-099 | |
| 0135 | 20 | GA | | 4-11 | 24-51-61 | K00101 | X1 | C | | | D40400J | 41 | | | 115-199 | |
| 0136 | 20 | GA | | 5-0 | 24-51-61 | K00101 | Y1 | C | | | D40400J | 42 | | | 001-099 | |
| 0136 | 20 | GA | | 4-11 | 24-51-61 | K00101 | Y1 | C | | | D40400J | 42 | | | 115-199 | |
| 0137 | 24 | GK | | 9-0 | 24-28-11 | C00816 | =L | D | | | D40400J | 8 | | | 001-099 | |
| 0137 | 24 | GK | | 8-9 | 24-28-11 | C00816 | =L | D | | | D40400J | 8 | | | 115-199 | |
| 0138 | 24 | GK | | 18-0 | 24-28-11 | C00815 | =L | D | | | D40400J | 9 | | | 001-099 | |
| 0138 | 24 | GK | | 17-2 | 24-28-11 | C00815 | =L | D | | | D40400J | 9 | | | 115-199 | |
| 0139 | 24 | GK | | 9-0 | 24-41-11 | C00320 | A2 | D | | | D40400J | 32 | | | 001-099 | |
| 0139 | 24 | GK | | 8-5 | 24-41-11 | C00320 | A2 | D | | | D40400J | 32 | | | 115-199 | |
| 0140 | 24 | GK | | 9-0 | 24-41-11 | C00320 | B2 | D | | | D40400J | 33 | | | 001-099 | |
| 0140 | 24 | GK | | 8-5 | 24-41-11 | C00320 | B2 | D | | | D40400J | 33 | | | 115-199 | |
| 0141 | 24 | GK | | 9-0 | 24-41-11 | C00320 | C2 | D | | | D40400J | 34 | | | 001-099 | |
| 0141 | 24 | GK | | 8-5 | 24-41-11 | C00320 | C2 | D | | | D40400J | 34 | | | 115-199 | |
| 0142 | 24 | GK | | 8-0 | 24-51-51 | TB0047X | A005 | BJ | | | D40400J | 4 | | | 001-099 | |
| 0142 | 24 | GK | | 3-2 | 24-51-51 | TB0047X | A005 | BJ | | | D40400J | 4 | | | 115-199 | |
| 0143 | 24 | GK | | 8-0 | 24-51-51 | TB0047X | B005 | BJ | | | D40400J | 3 | | | 001-099 | |
| 0143 | 24 | GK | | 3-2 | 24-51-51 | TB0047X | B005 | BJ | | | D40400J | 3 | | | 115-199 | |
| 0144 | 20 | GA | | 11-0 | 24-51-51 | TB0047X | D006 | BJ | | | K00102 | X1 | C | * | 001-099 | |
| 0144 | 20 | GA | | 3-2 | 24-51-51 | TB0047X | D006 | BJ | | | D40400J | 10 | | | 115-199 | |
| 0145 | 18 | GA | | 5-0 | 24-28-11 | C00905 | L2 | H | * | | C00815 | =B | D | | 001-099 | |
| 0145 | 18 | GA | | 4-1 | 24-28-11 | C00905 | L2 | H | * | | C00815 | =B | D | | 115-199 | |
| 0146 | 22 | GA | | 2-0 | 24-28-11 | C00320 | B1 | D | | | C00816 | =B | D | | 001-099 | |
| 0146 | 22 | GA | | 1-2 | 24-28-11 | C00320 | B1 | D | | | C00816 | =B | D | | 115-199 | |
| 0150 | 22 | GA | | 3-1 | 33-27-11 | D40956J | 11 | | | | TB0047Z | 10 | BJ | | 115-199 | |
| 0151 | 22 | GA | | 3-0 | 33-27-11 | D40956J | 10 | | | | TB0047Z | 8 | BJ | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 25

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1128 | 286N1128 | | | P34 MODULE WIRING (continued) | | | | | | | | | | | |
| 0152 | 22 | | GA | | 7-0 | 33-27-11 | D40956J | | | 9 | TB0047X | D005 | BJ | | 001-099 |
| 0152 | 22 | | GA | | 3-1 | 33-27-11 | D40956J | | | 9 | TB0047Y | A011 | BJ | | 115-199 |
| 0153 | 22 | | GA | | 5-0 | 33-27-21 | D40956J | | | 14 | TB0047Z | 0008 | BJ | | 115-199 |
| 0154 | 22 | | GA | | 3-1 | 33-27-21 | D40956J | | | 13 | TB0047Z | 10 | BJ | | 115-199 |
| 0165 | 24 | | GK | | 12-0 | 24-51-71 | D01732 | | | 23 | TB0047X | B006 | BJ | | 001-099 |
| 0165 | 24 | | GK | | 8-0 | 24-51-71 | D01732 | | | 23 | TB0047X | B023 | BJ | | 115-199 |
| 0166 | 24 | | GK | | 6-0 | 24-51-71 | D01732 | | | 24 | D40956J | 3 | | | ALL |
| 4001B | 24 | | GN | AA | 4-0 | 24-23-11 | D02228 | | | 3 | D40400J | 15 | | | 001-099 |
| 4001B | 24 | | GN | AA | 3-8 | 24-23-11 | D02228 | | | 3 | D40400J | 15 | | | 115-199 |
| 4001G | 24 | | GN | AA | 0-0 | 24-23-11 | D02228 | | | 4 | D40400J | 16 | | | ALL |
| 4001R | 24 | | GN | AA | 0-0 | 24-23-11 | D02228 | | | 1 | D40400J | 17 | | | ALL |
| 4001Y | 24 | | GN | AA | 0-0 | 24-23-11 | D02228 | | | 2 | D40400J | 18 | | | ALL |
| 4002B | 24 | | GN | BB | 5-0 | 24-23-12 | D02234 | | | 3 | D40400J | 19 | | | 001-099 |
| 4002B | 24 | | GN | BB | 4-8 | 24-23-12 | D02234 | | | 3 | D40400J | 19 | | | 115-199 |
| 4002G | 24 | | GN | BB | 0-0 | 24-23-12 | D02234 | | | 4 | D40400J | 20 | | | ALL |
| 4002R | 24 | | GN | BB | 0-0 | 24-23-12 | D02234 | | | 1 | D40400J | 21 | | | ALL |
| 4002Y | 24 | | GN | BB | 0-0 | 24-23-12 | D02234 | | | 2 | D40400J | 22 | | | ALL |
| 4003B | 24 | | GN | CC | 5-0 | 24-23-12 | D02236 | | | 1 | D40400J | 23 | | | 001-099 |
| 4003B | 24 | | GN | CC | 4-3 | 24-23-12 | D02236 | | | 1 | D40400J | 23 | | | 115-199 |
| 4003G | 24 | | GN | CC | 0-0 | 24-23-12 | D02236 | | | 4 | D40400J | 24 | | | ALL |
| 4003R | 24 | | GN | CC | 0-0 | 24-23-12 | D02236 | | | 3 | D40400J | 25 | | | ALL |
| 4003Y | 24 | | GN | CC | 0-0 | 24-23-12 | D02236 | | | 2 | D40400J | 26 | | | ALL |
| 4004B | 24 | | GN | DD | 3-0 | 24-41-11 | D01852 | | | 1 | D40400J | 27 | | | 001-099 |
| 4004B | 24 | | GN | DD | 3-4 | 24-41-11 | D01852 | | | 1 | D40400J | 27 | | | 115-199 |
| 4004G | 24 | | GN | DD | 0-0 | 24-41-11 | D01852 | | | 4 | D40400J | 28 | | | ALL |
| 4004R | 24 | | GN | DD | 0-0 | 24-41-11 | D01852 | | | 3 | D40400J | 29 | | | ALL |
| 4004Y | 24 | | GN | DD | 0-0 | 24-41-11 | D01852 | | | 2 | D40400J | 30 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1120

Page 26 End

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1130 | 286N1130 | | | P31 MODULE WIRING, LEFT GEN DISTR | | | | | | | | | | | |
| 0001 | 04 | | HA | | 1-5 | 24-21-11 | C00901 | L1 | H | *1 | C00902 | T1 | H | *1 | ALL |
| 0002 | 04 | | HA | | 1-5 | 24-21-11 | C00901 | L1 | H | *1 | C00902 | T1 | H | *1 | ALL |
| 0003 | 04 | | HA | | 1-7 | 24-21-11 | C00901 | L2 | H | *1 | C00902 | T2 | H | *1 | ALL |
| 0004 | 04 | | HA | | 1-7 | 24-21-11 | C00901 | L2 | H | *1 | C00902 | T2 | H | *1 | 001-099 |
| 0004 | 04 | | HA | | 1-6 | 24-21-11 | C00901 | L2 | H | *1 | C00902 | T2 | H | *1 | 115-199 |
| 0005 | 04 | | HA | | 1-9 | 24-21-11 | C00901 | L3 | H | *1 | C00902 | T3 | H | *1 | ALL |
| 0006 | 04 | | HA | | 1-9 | 24-21-11 | C00901 | L3 | H | *1 | C00902 | T3 | H | *1 | 001-099 |
| 0006 | 04 | | HA | | 1-8 | 24-21-11 | C00901 | L3 | H | *1 | C00902 | T3 | H | *1 | 115-199 |
| 0007 | 04 | | HA | | 1-1 | 24-21-11 | M00227 | A1 | H | * | C03015 | A1 | KA | | 001-099 |
| 0007 | 04 | | HA | | 2-6 | 24-21-11 | M10006 | A1 | H | * | C00902 | T1 | H | *2 | 115-199 |
| 0008 | 04 | | HA | | 1-1 | 24-21-11 | M00227 | B1 | H | * | C03015 | B1 | KA | | 001-099 |
| 0008 | 04 | | HA | | 2-5 | 24-21-11 | M10006 | B1 | H | * | C00902 | T2 | H | *2 | 115-199 |
| 0009 | 04 | | HA | | 1-2 | 24-21-11 | M00227 | C1 | H | * | C03015 | C1 | KA | | 001-099 |
| 0009 | 04 | | HA | | 2-6 | 24-21-11 | M10006 | C1 | H | * | C00902 | T3 | H | *2 | 115-199 |
| 0010 | 04 | | HA | | 3-5 | 24-21-11 | C00311 | A1 | KA | | C00902 | T1 | H | *2 | ALL |
| 0011 | 04 | | HA | | 3-4 | 24-21-11 | C00311 | B1 | KA | | C00902 | T2 | H | *2 | 001-099 |
| 0011 | 04 | | HA | | 3-5 | 24-21-11 | C00311 | B1 | KA | | C00902 | T2 | H | *2 | 115-199 |
| 0012 | 04 | | HA | | 3-3 | 24-21-11 | C00311 | C1 | KA | | C00902 | T3 | H | *2 | ALL |
| 0013 | 04 | | HA | | 0-11 | 24-21-11 | M10005 | A1 | H | * | M00227 | A1 | H | * | ALL |
| 0014 | 04 | | HA | | 0-11 | 24-21-11 | M10005 | B1 | H | * | M00227 | B1 | H | * | 001-099 |
| 0014 | 04 | | HA | | 0-10 | 24-21-11 | M10005 | B1 | H | * | M00227 | B1 | H | * | 115-199 |
| 0015 | 04 | | HA | | 0-11 | 24-21-11 | M10005 | C1 | H | * | M00227 | C1 | H | * | 001-099 |
| 0015 | 04 | | HA | | 0-10 | 24-21-11 | M10005 | C1 | H | * | M00227 | C1 | H | * | 115-199 |
| 0016 | 04 | | HA | | 2-5 | 24-21-11 | M10005 | A1 | H | * | M10006 | A1 | H | * | ALL |
| 0017 | 04 | | HA | | 2-2 | 24-21-11 | M10005 | B1 | H | * | M10006 | B1 | H | * | ALL |
| 0018 | 04 | | HA | | 2-1 | 24-21-11 | M10005 | C1 | H | * | M10006 | C1 | H | * | ALL |
| 0019 | 04 | | HA | | 2-6 | 24-21-11 | C00902 | T1 | H | *2 | M10006 | A1 | H | * | 001-099 |
| 0019 | 04 | | HA | | 0-11 | 24-21-11 | C03015 | A1 | KA | | C03027 | A1 | KA | | 115-199 |
| 0020 | 04 | | HA | | 2-6 | 24-21-11 | C00902 | T2 | H | *2 | M10006 | B1 | H | * | 001-099 |
| 0020 | 04 | | HA | | 0-11 | 24-21-11 | C03015 | B1 | KA | | C03027 | B1 | KA | | 115-199 |
| 0021 | 04 | | HA | | 2-6 | 24-21-11 | C00902 | T3 | H | *2 | M10006 | C1 | H | * | 001-099 |
| 0021 | 04 | | HA | | 0-11 | 24-21-11 | C03015 | C1 | KA | | C03027 | C1 | KA | | 115-199 |
| 0022 | 04 | | HA | | 0-10 | 24-21-11 | C03015 | A1 | KA | | C00311 | A1 | KA | | ALL |
| 0023 | 04 | | HA | | 0-9 | 24-21-11 | C03015 | B1 | KA | | C00311 | B1 | KA | | ALL |
| 0024 | 04 | | HA | | 0-10 | 24-21-11 | C03015 | C1 | KA | | C00311 | C1 | KA | | ALL |
| 0025 | 08 | | HA | | 3-0 | 24-51-14 | C00311 | A2 | D | | TB5031 | 4 | E | | 001-099 |
| 0025 | 08 | | HA | | 2-9 | 24-51-14 | C00311 | A2 | D | | TB5031 | 4 | E | | 115-199 |
| 0026 | 08 | | HA | | 3-0 | 24-51-14 | C00311 | B2 | D | | TB5031 | 5 | E | | 001-099 |
| 0026 | 08 | | HA | | 2-9 | 24-51-14 | C00311 | B2 | D | | TB5031 | 5 | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1130 | 286N1130 | | | P31 MODULE WIRING, LEFT GEN DISTR (continued) | | | | | | | | | | | |
| 0027 | 08 | | HA | | 3-0 | 24-51-14 | C00311 | C2 | D | | TB5031 | 6 | E | | 001-099 |
| 0027 | 08 | | HA | | 2-9 | 24-51-14 | C00311 | C2 | D | | TB5031 | 6 | E | | 115-199 |
| 0028 | 08 | | HA | | 3-2 | 24-51-11 | C03015 | A2 | D | | TB5031 | 1 | E | | 001-099 |
| 0028 | 08 | | HA | | 3-0 | 24-51-11 | C03015 | A2 | D | | TB5031 | 1 | E | | 115-199 |
| 0029 | 08 | | HA | | 3-1 | 24-51-11 | C03015 | B2 | D | | TB5031 | 2 | E | | 001-099 |
| 0029 | 08 | | HA | | 2-11 | 24-51-11 | C03015 | B2 | D | | TB5031 | 2 | E | | 115-199 |
| 0030 | 08 | | HA | | 3-1 | 24-51-11 | C03015 | C2 | D | | TB5031 | 3 | E | | 001-099 |
| 0030 | 08 | | HA | | 2-11 | 24-51-11 | C03015 | C2 | D | | TB5031 | 3 | E | | 115-199 |
| 0031 | 04 | | HA | | 1-1 | 24-21-11 | C03027 | A1 | KA | | M00227 | A1 | H | * | 115-199 |
| 0032 | 04 | | HA | | 1-1 | 24-21-11 | C03027 | B1 | KA | | M00227 | B1 | H | * | 115-199 |
| 0033 | 04 | | HA | | 1-2 | 24-21-11 | C03027 | C1 | KA | | M00227 | C1 | H | * | 115-199 |
| 0034 | 08 | | HA | | 2-10 | 24-51-14 | C03027 | A2 | D | | TB5031 | 7 | E | | 115-199 |
| 0035 | 08 | | HA | | 2-10 | 24-51-14 | C03027 | B2 | D | | TB5031 | 8 | E | | 115-199 |
| 0036 | 08 | | HA | | 2-9 | 24-51-14 | C03027 | C2 | D | | TB5031 | 9 | E | | 115-199 |
| W1132 | 286N1132 | | | P32 MODULE WIRING, RIGHT GEN DISTR | | | | | | | | | | | |
| 0001 | 04 | | HA | | 1-7 | 24-21-21 | C00903 | L1 | H | *1 | C00904 | T1 | H | *1 | ALL |
| 0002 | 04 | | HA | | 1-7 | 24-21-21 | C00903 | L1 | H | *1 | C00904 | T1 | H | *1 | ALL |
| 0003 | 04 | | HA | | 1-6 | 24-21-21 | C00903 | L2 | H | *1 | C00904 | T2 | H | *1 | ALL |
| 0004 | 04 | | HA | | 1-6 | 24-21-21 | C00903 | L2 | H | *1 | C00904 | T2 | H | *1 | ALL |
| 0005 | 04 | | HA | | 1-5 | 24-21-21 | C00903 | L3 | H | *1 | C00904 | T3 | H | *1 | ALL |
| 0006 | 04 | | HA | | 1-5 | 24-21-21 | C00903 | L3 | H | *1 | C00904 | T3 | H | *1 | ALL |
| 0007 | 04 | | HA | | 1-5 | 24-21-21 | M00546 | A1 | H | * | C03016 | A1 | KA | | 001-099 |
| 0007 | 04 | | HA | | 2-8 | 24-21-21 | M10022 | A1 | H | * | C00904 | T1 | H | *2 | 115-199 |
| 0008 | 04 | | HA | | 1-5 | 24-21-21 | M00546 | B1 | H | * | C03016 | B1 | KA | | 001-099 |
| 0008 | 04 | | HA | | 2-7 | 24-21-21 | M10022 | B1 | H | * | C00904 | T2 | H | *2 | 115-199 |
| 0009 | 04 | | HA | | 1-5 | 24-21-21 | M00546 | C1 | H | * | C03016 | C1 | KA | | 001-099 |
| 0009 | 04 | | HA | | 2-7 | 24-21-21 | M10022 | C1 | H | * | C00904 | T3 | H | *2 | 115-199 |
| 0010 | 04 | | HA | | 3-6 | 24-21-21 | C00315 | A1 | KA | | C00904 | T1 | H | *2 | 001-099 |
| 0010 | 04 | | HA | | 3-5 | 24-21-21 | C00315 | A1 | KA | | C00904 | T1 | H | *2 | 115-199 |
| 0011 | 04 | | HA | | 3-4 | 24-21-21 | C00315 | B1 | KA | | C00904 | T2 | H | *2 | ALL |
| 0012 | 04 | | HA | | 3-6 | 24-21-21 | C00315 | C1 | KA | | C00904 | T3 | H | *2 | 001-099 |
| 0012 | 04 | | HA | | 3-5 | 24-21-21 | C00315 | C1 | KA | | C00904 | T3 | H | *2 | 115-199 |
| 0013 | 04 | | HA | | 1-5 | 24-21-21 | M00225 | A1 | H | * | C03026 | A1 | KA | | 115-199 |
| 0014 | 04 | | HA | | 1-5 | 24-21-21 | M00225 | B1 | H | * | C03026 | B1 | KA | | 115-199 |
| 0015 | 04 | | HA | | 1-5 | 24-21-21 | M00225 | C1 | H | * | C03026 | C1 | KA | | 115-199 |
| 0016 | 04 | | HA | | 1-9 | 24-21-21 | M00546 | A1 | H | * | M10001 | A1 | H | * | 001-099 |
| 0016 | 04 | | HA | | 1-9 | 24-21-21 | M00225 | A1 | H | * | M10001 | A1 | H | * | 115-199 |
| 0017 | 04 | | HA | | 1-11 | 24-21-21 | M00546 | B1 | H | * | M10001 | B1 | H | * | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 2

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|--------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1132 | 286N1132 | | | P32 MODULE WIRING, RIGHT GEN DISTR (continued) | | | | | | | | | | | |
| 0017 | 04 | HA | | | 1-11 | 24-21-21 | M00225 | B1 | H | * | M10001 | B1 | H | * | 115-199 |
| 0018 | 04 | HA | | | 2-0 | 24-21-21 | M00546 | C1 | H | * | M10001 | C1 | H | * | 001-099 |
| 0018 | 04 | HA | | | 2-0 | 24-21-21 | M00225 | C1 | H | * | M10001 | C1 | H | * | 115-199 |
| 0019 | 04 | HA | | | 1-1 | 24-21-21 | M10022 | A1 | H | * | M10001 | A1 | H | * | ALL |
| 0020 | 04 | HA | | | 1-1 | 24-21-21 | M10022 | B1 | H | * | M10001 | B1 | H | * | ALL |
| 0021 | 04 | HA | | | 1-1 | 24-21-21 | M10022 | C1 | H | * | M10001 | C1 | H | * | ALL |
| 0022 | 04 | HA | | | 2-8 | 24-21-21 | M10022 | A1 | H | * | C00904 | T1 | H | *2 | 001-099 |
| 0022 | 04 | HA | | | 1-1 | 24-21-21 | C03026 | A1 | KA | | C00316 | A1 | KA | | 115-199 |
| 0023 | 04 | HA | | | 2-7 | 24-21-21 | M10022 | B1 | H | * | C00904 | T2 | H | *2 | 001-099 |
| 0023 | 04 | HA | | | 1-1 | 24-21-21 | C03026 | B1 | KA | | C00316 | B1 | KA | | 115-199 |
| 0024 | 04 | HA | | | 2-7 | 24-21-21 | M10022 | C1 | H | * | C00904 | T3 | H | *2 | 001-099 |
| 0024 | 04 | HA | | | 1-1 | 24-21-21 | C03026 | C1 | KA | | C00316 | C1 | KA | | 115-199 |
| 0025 | 04 | HA | | | 0-8 | 24-21-21 | C03016 | A1 | KA | | C00316 | A1 | KA | | ALL |
| 0026 | 04 | HA | | | 0-8 | 24-21-21 | C03016 | B1 | KA | | C00316 | B1 | KA | | ALL |
| 0027 | 04 | HA | | | 0-8 | 24-21-21 | C03016 | C1 | KA | | C00316 | C1 | KA | | ALL |
| 0028 | 04 | HA | | | 1-1 | 24-21-21 | C00316 | A1 | KA | | C03026 | A1 | KA | | 001-099 |
| 0028 | 04 | HA | | | 0-10 | 24-21-21 | C03016 | A1 | KA | | C00315 | A1 | KA | | 115-199 |
| 0029 | 04 | HA | | | 1-1 | 24-21-21 | C00316 | B1 | KA | | C03026 | B1 | KA | | 001-099 |
| 0029 | 04 | HA | | | 0-10 | 24-21-21 | C03016 | B1 | KA | | C00315 | B1 | KA | | 115-199 |
| 0030 | 04 | HA | | | 1-1 | 24-21-21 | C00316 | C1 | KA | | C03026 | C1 | KA | | 001-099 |
| 0030 | 04 | HA | | | 0-10 | 24-21-21 | C03016 | C1 | KA | | C00315 | C1 | KA | | 115-199 |
| 0031 | 08 | HA | | | 2-5 | 24-51-52 | C00316 | A2 | D | | TB5032 | 1 | E | | ALL |
| 0032 | 08 | HA | | | 2-5 | 24-51-52 | C00316 | B2 | D | | TB5032 | 2 | E | | ALL |
| 0033 | 08 | HA | | | 2-5 | 24-51-52 | C00316 | C2 | D | | TB5032 | 3 | E | | ALL |
| 0034 | 08 | HA | | | 2-5 | 24-51-21 | C03016 | A2 | D | | TB5032 | 4 | E | | ALL |
| 0035 | 08 | HA | | | 2-6 | 24-51-21 | C03016 | B2 | D | | TB5032 | 5 | E | | ALL |
| 0036 | 08 | HA | | | 2-6 | 24-51-21 | C03016 | C2 | D | | TB5032 | 6 | E | | ALL |
| 0037 | 08 | HA | | | 3-1 | 24-51-24 | C00315 | A2 | D | | TB5032 | 7 | E | | 001-099 |
| 0037 | 08 | HA | | | 3-0 | 24-51-24 | C00315 | A2 | D | | TB5032 | 7 | E | | 115-199 |
| 0038 | 08 | HA | | | 3-1 | 24-51-24 | C00315 | B2 | D | | TB5032 | 8 | E | | ALL |
| 0039 | 08 | HA | | | 3-1 | 24-51-24 | C00315 | C2 | D | | TB5032 | 9 | E | | ALL |
| 0040 | 08 | HA | | | 3-7 | 24-51-24 | C03026 | A2 | D | | TB5032 | 10 | E | | 115-199 |
| 0041 | 08 | HA | | | 3-7 | 24-51-24 | C03026 | B2 | D | | TB5032 | 11 | E | | 115-199 |
| 0042 | 08 | HA | | | 3-7 | 24-51-24 | C03026 | C2 | D | | TB5032 | 12 | E | | 115-199 |
| 0043 | 10 | HA | | | 4-0 | 24-32-41 | C03000 | A2 | D | | TB5032 | 13 | E | | 001-099 |
| 0043 | 10 | HA | | | 3-7 | 24-32-41 | C03000 | A2 | D | | TB5032 | 13 | E | | 115-199 |
| 0044 | 10 | HA | | | 3-7 | 24-32-41 | C03000 | B2 | D | | TB5032 | 14 | E | | ALL |
| 0045 | 10 | HA | | | 4-0 | 24-32-41 | C03000 | C2 | D | | TB5032 | 15 | E | | 001-099 |
| 0045 | 10 | HA | | | 3-7 | 24-32-41 | C03000 | C2 | D | | TB5032 | 15 | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 3

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1132 | 286N1132 | | | P32 MODULE WIRING, RIGHT GEN DISTR (continued) | | | | | | | | | | | |
| 0046 | 08 | | HA | | 2-7 | 24-51-21 | C03000 | A1 | D | | C00903 | L1 | H | | ALL |
| 0047 | 08 | | HA | | 2-9 | 24-51-21 | C03000 | B1 | D | | C00903 | L2 | H | | ALL |
| 0048 | 08 | | HA | | 2-9 | 24-51-21 | C03000 | C1 | D | | C00903 | L3 | H | | ALL |
| 0053 | 04 | | HA | | 0-11 | 24-21-21 | C03026 | C1 | KA | | C00315 | C1 | KA | | 001-099 |
| 0054 | 04 | | HA | | 0-11 | 24-21-21 | C03026 | B1 | KA | | C00315 | B1 | KA | | 001-099 |
| 0055 | 04 | | HA | | 0-11 | 24-21-21 | C03026 | A1 | KA | | C00315 | A1 | KA | | 001-099 |
| 0059 | 08 | | HA | | 3-6 | 24-51-24 | C03026 | A2 | D | | TB5032 | 10 | E | | 001-099 |
| 0060 | 08 | | HA | | 3-6 | 24-51-24 | C03026 | B2 | D | | TB5032 | 11 | E | | 001-099 |
| 0061 | 08 | | HA | | 3-6 | 24-51-24 | C03026 | C2 | D | | TB5032 | 12 | E | | 001-099 |
| W1134 | 286N1134 | | | P34 MODULE WIRING, APU / EXT PWR DISTR | | | | | | | | | | | |
| 0001 | 08 | | HA | | 5-6 | 24-51-52 | K00103 | A3 | F | | C00306 | A2 | D | | 001-099 |
| 0001 | 08 | | HA | | 5-0 | 24-51-52 | K00103 | A3 | F | | C00306 | A2 | D | | 115-199 |
| 0002 | 08 | | HA | | 5-6 | 24-51-52 | K00103 | B3 | F | | C00306 | B2 | D | | 001-099 |
| 0002 | 08 | | HA | | 5-0 | 24-51-52 | K00103 | B3 | F | | C00306 | B2 | D | | 115-199 |
| 0003 | 08 | | HA | | 5-0 | 24-51-52 | K00103 | C3 | F | | C00306 | C2 | D | | 001-099 |
| 0003 | 08 | | HA | | 4-8 | 24-51-52 | K00103 | C3 | F | | C00306 | C2 | D | | 115-199 |
| 0004 | 08 | | HA | | 6-10 | 24-51-52 | K00103 | A1 | F | | C00322 | A2 | D | | 001-099 |
| 0004 | 08 | | HA | | 6-5 | 24-51-52 | K00103 | A1 | F | | C00322 | A2 | D | | 115-199 |
| 0005 | 08 | | HA | | 7-6 | 24-51-52 | K00103 | B1 | F | | C00322 | B2 | D | | 001-099 |
| 0005 | 08 | | HA | | 6-8 | 24-51-52 | K00103 | B1 | F | | C00322 | B2 | D | | 115-199 |
| 0006 | 08 | | HA | | 7-6 | 24-51-52 | K00103 | C1 | F | | C00322 | C2 | D | | 001-099 |
| 0006 | 08 | | HA | | 7-2 | 24-51-52 | K00103 | C1 | F | | C00322 | C2 | D | | 115-199 |
| 0007 | 08 | | HA | | 3-0 | 24-51-52 | C00306 | A1 | D | | K00114 | A1 | H | * | 001-099 |
| 0007 | 08 | | HA | | 2-9 | 24-51-52 | C00306 | A1 | D | | K00114 | A1 | H | * | 115-199 |
| 0008 | 08 | | HA | | 2-11 | 24-51-52 | C00306 | B1 | D | | K00114 | B1 | H | * | 001-099 |
| 0008 | 08 | | HA | | 2-7 | 24-51-52 | C00306 | B1 | D | | K00114 | B1 | H | * | 115-199 |
| 0009 | 08 | | HA | | 3-0 | 24-51-52 | C00306 | C1 | D | | K00114 | C1 | H | * | 001-099 |
| 0009 | 08 | | HA | | 2-6 | 24-51-52 | C00306 | C1 | D | | K00114 | C1 | H | * | 115-199 |
| 0010 | 08 | | HA | | 3-6 | 24-51-52 | C00322 | A1 | D | | C00905 | L3 | H | * | 001-099 |
| 0010 | 08 | | HA | | 3-0 | 24-51-52 | C00322 | A1 | D | | C00905 | L3 | H | * | 115-199 |
| 0011 | 08 | | HA | | 3-6 | 24-51-52 | C00322 | B1 | D | | C00905 | L2 | H | * | 001-099 |
| 0011 | 08 | | HA | | 2-11 | 24-51-52 | C00322 | B1 | D | | C00905 | L2 | H | * | 115-199 |
| 0012 | 08 | | HA | | 3-6 | 24-51-52 | C00322 | C1 | D | | C00905 | L1 | H | * | 001-099 |
| 0012 | 08 | | HA | | 3-1 | 24-51-52 | C00322 | C1 | D | | C00905 | L1 | H | * | 115-199 |
| 0013 | 08 | | HA | | 3-6 | 24-51-61 | C00321 | A1 | D | | C00905 | L3 | H | * | 001-099 |
| 0013 | 08 | | HA | | 3-2 | 24-51-61 | C00321 | A1 | D | | C00905 | L3 | H | * | 115-199 |
| 0014 | 08 | | HA | | 3-6 | 24-51-61 | C00321 | B1 | D | | C00905 | L2 | H | * | 001-099 |
| 0014 | 08 | | HA | | 3-3 | 24-51-61 | C00321 | B1 | D | | C00905 | L2 | H | * | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 4

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1134 | 286N1134 | | | P34 MODULE WIRING, APU / EXT PWR DISTR (continued) | | | | | | | | | | | |
| 0015 | 08 | HA | | | 3-6 | 24-51-61 | C00321 | C1 | D | | C00905 | L1 | H | * | 001-099 |
| 0015 | 08 | HA | | | 3-4 | 24-51-61 | C00321 | C1 | D | | C00905 | L1 | H | * | 115-199 |
| 0016 | 14 | GA | | | 7-0 | 24-51-61 | K00101 | A3 | F | | C00321 | A2 | D | | 001-099 |
| 0016 | 10 | GA | | | 7-0 | 24-51-61 | K00101 | A3 | F | | C00321 | A2 | D | | 115-199 |
| 0017 | 14 | GA | | | 8-0 | 24-51-61 | K00101 | B3 | F | | C00321 | B2 | D | | 001-099 |
| 0017 | 10 | GA | | | 7-0 | 24-51-61 | K00101 | B3 | F | | C00321 | B2 | D | | 115-199 |
| 0018 | 14 | GA | | | 8-0 | 24-51-61 | K00101 | C3 | F | | C00321 | C2 | D | | 001-099 |
| 0018 | 10 | GA | | | 8-0 | 24-51-61 | K00101 | C3 | F | | C00321 | C2 | D | | 115-199 |
| 0019 | 14 | GA | | | 5-0 | 24-51-61 | K00101 | A1 | F | | C00305 | A2 | D | | 001-099 |
| 0019 | 10 | GA | | | 6-0 | 24-51-61 | K00101 | A1 | F | | C00305 | A2 | D | | 115-199 |
| 0020 | 14 | GA | | | 5-0 | 24-51-61 | K00101 | B1 | F | | C00305 | B2 | D | | 001-099 |
| 0020 | 10 | GA | | | 5-0 | 24-51-61 | K00101 | B1 | F | | C00305 | B2 | D | | 115-199 |
| 0021 | 14 | GA | | | 5-0 | 24-51-61 | K00101 | C1 | F | | C00305 | C2 | D | | 001-099 |
| 0021 | 10 | GA | | | 5-0 | 24-51-61 | K00101 | C1 | F | | C00305 | C2 | D | | 115-199 |
| 0022 | 08 | HA | | | 2-9 | 24-51-61 | K00114 | A1 | H | * | C00305 | A1 | D | | 001-099 |
| 0022 | 08 | HA | | | 2-6 | 24-51-61 | K00114 | A1 | H | * | C00305 | A1 | D | | 115-199 |
| 0023 | 08 | HA | | | 2-9 | 24-51-61 | K00114 | B1 | H | * | C00305 | B1 | D | | 001-099 |
| 0023 | 08 | HA | | | 2-4 | 24-51-61 | K00114 | B1 | H | * | C00305 | B1 | D | | 115-199 |
| 0024 | 08 | HA | | | 2-9 | 24-51-61 | K00114 | C1 | H | * | C00305 | C1 | D | | 001-099 |
| 0024 | 08 | HA | | | 2-5 | 24-51-61 | K00114 | C1 | H | * | C00305 | C1 | D | | 115-199 |
| 0025 | 10 | GA | | | 4-0 | 24-51-61 | K00101 | A2 | F | | C00309 | A1 | D | | 115-199 |
| 0026 | 10 | GA | | | 4-0 | 24-51-61 | K00101 | B2 | F | | C00309 | B1 | D | | 115-199 |
| 0027 | 10 | GA | | | 5-0 | 24-51-61 | K00101 | C2 | F | | C00309 | C1 | D | | 115-199 |
| 0030 | 08 | HA | | | 1-0 | 24-51-52 | K00103 | A2 | F | | K00102 | A1 | F | | 001-099 |
| 0031 | 08 | HA | | | 1-0 | 24-51-52 | K00103 | B2 | F | | K00102 | B1 | F | | 001-099 |
| 0032 | 08 | HA | | | 1-0 | 24-51-52 | K00103 | C2 | F | | K00102 | C1 | F | | 001-099 |
| W1136 | 286N1136 | | | P31 MODULE WIRING | | | | | | | | | | | |
| 0001 | 18 | GA | | | 4-0 | 24-21-11 | C00902 | T3 | H | | L00012 | 1 | C | | 001-099 |
| 0001 | 18 | GA | | | 5-0 | 24-21-11 | C00902 | T3 | H | | L00012 | 1 | C | | 115-199 |
| 0002 | 18 | GA | | | 4-9 | 24-21-11 | GD02340 | AC.. | 2 | | L00012 | 2 | C | | 001-099 |
| 0002 | 18 | GA | | | 6-0 | 24-21-11 | GD02340 | AC.. | 2 | | L00012 | 2 | C | | 115-199 |
| 0003 | 18 | GA | | | 2-8 | 24-21-11 | C00901 | T3 | H | * | L00011 | 1 | C | | 001-099 |
| 0003 | 18 | GA | | | 4-0 | 24-21-11 | C00901 | T3 | H | * | L00011 | 1 | C | | 115-199 |
| 0004 | 18 | GA | | | 4-9 | 24-21-11 | GD02340 | AC.. | 2 | | L00011 | 2 | C | | 001-099 |
| 0004 | 18 | GA | | | 6-0 | 24-21-11 | GD02340 | AC.. | 2 | | L00011 | 2 | C | | 115-199 |
| 0005 | 18 | GA | | | 4-9 | 24-21-51 | GD02340 | AC.. | 2 | | L00007 | 2 | C | | 001-099 |
| 0005 | 18 | GA | | | 6-0 | 24-21-51 | GD02340 | AC.. | 2 | | L00007 | 2 | C | | 115-199 |
| 0006 | 18 | GA | | | 5-2 | 24-21-51 | C00902 | L3 | H | | L00007 | 1 | C | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 5

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|-------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1136 | 286N1136 | | | P31 MODULE WIRING (continued) | | | | | | | | | | | |
| 0006 | 18 | | GA | | 6-0 | 24-21-51 | C00902 | L3 | H | | L00007 | 1 | C | | 115-199 |
| 0007 | 18 | | GA | | 3-11 | 24-22-12 | GD02340 | AC.. | 2 | | D02182 | X2 | | | 001-099 |
| 0007 | 18 | | GA | | 5-0 | 24-22-12 | GD02340 | AC.. | 2 | | D02182 | X2 | | | 115-199 |
| 0008 | 20 | | GA | | 6-10 | 29-11-22 | GD02340 | ST.. | 2 | | D03062 | 15 | | | 001-099 |
| 0008 | 20 | | GA | | 7-0 | 29-11-22 | GD02340 | ST.. | 2 | | D03062 | 15 | | | 115-199 |
| 0009 | 20 | | GA | | 6-10 | 29-11-22 | GD02340 | DC.. | 2 | | D03062 | 10 | | | 001-099 |
| 0009 | 20 | | GA | | 1-0 | 29-11-22 | SM00009 | | WI | | D03062 | 10 | | | 115-199 |
| 0010 | 22 | | GA | | 0-7 | 29-11-22 | D03062 | | 11 | | D03062 | 12 | | | 001-099 |
| 0010 | 22 | | GA | | 1-0 | 29-11-22 | D03062 | | 11 | | D03062 | 12 | | | 115-199 |
| 0011 | 20 | | GA | | 5-2 | 29-11-31 | GD02340 | DC.. | 2 | | D02934 | 10 | | | 001-099 |
| 0011 | 20 | | GA | | 1-0 | 29-11-31 | SM00010 | | WI | | D02934 | 10 | | | 115-199 |
| 0012 | 20 | | GA | | 5-2 | 29-11-31 | GD02340 | ST.. | 2 | | D02934 | 15 | | | 001-099 |
| 0012 | 20 | | GA | | 6-0 | 29-11-31 | GD02340 | ST.. | 2 | | D02934 | 15 | | | 115-199 |
| 0013 | 22 | | GA | | 0-7 | 29-11-31 | D02934 | | 11 | | D02934 | 12 | | | 001-099 |
| 0013 | 22 | | GA | | 1-0 | 29-11-31 | D02934 | | 11 | | D02934 | 12 | | | 115-199 |
| 0014 | 20 | | GA | | 6-6 | 25-31-33 | GD02340 | DC.. | 2 | | D02352 | 10 | | | 001-099 |
| 0014 | 20 | | GA | | 7-0 | 25-31-33 | GD02340 | DC.. | 2 | | D02352 | 10 | | | 115-199 |
| 0015 | 16 | | GA | | 0-7 | 29-11-22 | D03062 | | 8 16 | | SM00004 | | WI | | 001-099 |
| 0015 | 16 | | GA | | 1-0 | 29-11-22 | D03062 | | 8 16 | | SM00004 | | WI | | 115-199 |
| 0016 | 16 | | GA | | 0-7 | 29-11-22 | D03062 | | 18 16 | | SM00004 | | WI | | 001-099 |
| 0016 | 16 | | GA | | 1-0 | 29-11-22 | D03062 | | 18 16 | | SM00004 | | WI | | 115-199 |
| 0017 | 16 | | GA | | 4-4 | 29-11-31 | D40580J | | 2 16 | | SM00003 | | WI | | 001-099 |
| 0017 | 16 | | GA | | 5-0 | 29-11-31 | D40580J | | 2 16 | | SM00003 | | WI | | 115-199 |
| 0018 | 16 | | GA | | 0-7 | 29-11-31 | D02934 | | 18 16 | | SM00003 | | WI | | 001-099 |
| 0018 | 16 | | GA | | 1-0 | 29-11-31 | D02934 | | 18 16 | | SM00003 | | WI | | 115-199 |
| 0019 | 24 | | GK | | 2-2 | 24-51-31 | D01730 | | 26 | | TB0131Y | C012 | BJ | | 001-099 |
| 0019 | 24 | | GK | | 3-0 | 24-51-31 | D01730 | | 26 | | TB0131Y | C012 | BJ | | 115-199 |
| 0020 | 22 | | GA | | 3-11 | 29-11-31 | D02934 | | 5 | | SM00001 | | WI | | 001-099 |
| 0020 | 22 | | GA | | 1-0 | 29-11-31 | D02934 | | 5 | | SM00001 | | WI | | 115-199 |
| 0021 | 22 | | GA | | 3-11 | 29-11-31 | D02934 | | 6 | | SM00002 | | WI | | 001-099 |
| 0021 | 22 | | GA | | 1-0 | 29-11-31 | D02934 | | 6 | | SM00002 | | WI | | 115-199 |
| 0022 | 22 | | GA | | 1-3 | 29-11-31 | D41318J | | 8 | | SM00001 | | WI | | 001-099 |
| 0022 | 22 | | GA | | 5-0 | 29-11-31 | D41318J | | 8 | | SM00001 | | WI | | 115-199 |
| 0023 | 22 | | GA | | 1-3 | 29-11-31 | D41318J | | 9 | | SM00002 | | WI | | 001-099 |
| 0023 | 22 | | GA | | 5-0 | 29-11-31 | D41318J | | 9 | | SM00002 | | WI | | 115-199 |
| 0039 | 18 | | GA | | 2-11 | 25-31-33 | D04494 | | B2 | | D41104J | 4 | | | 001-099 |
| 0040 | 18 | | GA | | 4-10 | 25-31-33 | D04494 | | B3 | | D02352 | 8 18 | | | 001-099 |
| 0041 | 24 | | GK | | 2-11 | 24-51-71 | D04494 | | X1 | | D41104J | 1 | | | 001-099 |
| 0042 | 24 | | GK | | 2-11 | 24-51-71 | D04494 | | X2 | | D41104J | 2 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 6

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1136 | 286N1136 | | | P31 MODULE WIRING (continued) | | | | | | | | | | | |
| 0043 | 22 | GA | | | 2-10 | 29-11-31 | D02182 | C3 | | | D41318J | 26 | | | 001-099 |
| 0043 | 22 | GA | | | 4-0 | 29-11-31 | D02182 | C3 | | | D41318J | 26 | | | 115-199 |
| 0044 | 22 | GA | | | 3-4 | 29-11-31 | D02182 | C2 | | | D40392J | 25 | | | 001-099 |
| 0044 | 22 | GA | | | 4-0 | 29-11-31 | D02182 | C2 | | | D40392J | 25 | | | 115-199 |
| 0047 | 20 | GA | | | 7-0 | 29-11-22 | SM00009 | | WI | | TB0131X | A009 | BJ | | 115-199 |
| 0048 | 20 | GA | | | 6-0 | 29-11-31 | SM00010 | | WI | | TB0131X | B009 | BJ | | 115-199 |
| 0052 | 20 | GA | | | 2-11 | 25-31-11 | D04494 | C2 | | | D41318J | 29 | | | 001-099 |
| 0053 | 20 | GA | | | 2-11 | 25-31-11 | D04494 | C3 | | | D41318J | 7 | | | 001-099 |
| 0061 | 24 | GK | | | 2-7 | 24-27-11 | TB0131A | A013 | 2 | | D41318J | 22 | | | 001-099 |
| 0061 | 24 | GK | | | 3-0 | 24-27-11 | TB0131A | A013 | 2 | | D41318J | 22 | | | 115-199 |
| 0062 | 24 | GK | | | 2-0 | 24-27-11 | TB0131A | C013 | 2 | | D40392J | 13 | | | 001-099 |
| 0062 | 24 | GK | | | 3-0 | 24-27-11 | TB0131A | C013 | 2 | | D40392J | 13 | | | 115-199 |
| 0100 | 18 | GA | | | 4-6 | 24-21-11 | C00901 | T1 | H | | D40392J | 27 | | | 001-099 |
| 0100 | 18 | GA | | | 5-0 | 24-21-11 | C00901 | T1 | H | | D40392J | 27 | | | 115-199 |
| 0101 | 18 | GA | | | 4-6 | 24-21-11 | C00901 | T2 | H | * | D40392J | 28 | | | 001-099 |
| 0101 | 18 | GA | | | 5-0 | 24-21-11 | C00901 | T2 | H | * | D40392J | 28 | | | 115-199 |
| 0102 | 18 | GA | | | 4-5 | 24-21-11 | C00901 | T3 | H | * | D40392J | 29 | | | 001-099 |
| 0102 | 18 | GA | | | 5-0 | 24-21-11 | C00901 | T3 | H | * | D40392J | 29 | | | 115-199 |
| 0103 | 20 | GA | | | 3-4 | 24-22-12 | D02182 | A3 | | | D40392J | 34 | | | 001-099 |
| 0103 | 20 | GA | | | 4-0 | 24-22-12 | D02182 | A3 | | | D40392J | 34 | | | 115-199 |
| 0104 | 18 | GA | | | 2-4 | 24-22-12 | C00902 | L2 | H | | D40392J | 15 | | | 001-099 |
| 0104 | 18 | GA | | | 3-0 | 24-22-12 | C00902 | L2 | H | | D40392J | 15 | | | 115-199 |
| 0107 | 18 | GA | | | 4-0 | 24-22-11 | C00901 | L2 | H | | D40392J | 1 | | | 001-099 |
| 0107 | 18 | GA | | | 5-0 | 24-22-11 | C00901 | L2 | H | | D40392J | 1 | | | 115-199 |
| 0108 | 20 | GA | | | 4-7 | 24-22-11 | D01728 | 21 | | | D41318J | 30 | | | 001-099 |
| 0108 | 20 | GA | | | 7-0 | 24-22-11 | D01728 | 21 | | | D41318J | 30 | | | 115-199 |
| 0109 | 20 | GA | | | 4-0 | 24-22-11 | D01728 | 39 | | | D40392J | 31 | | | 001-099 |
| 0109 | 20 | GA | | | 5-0 | 24-22-11 | D01728 | 39 | | | D40392J | 31 | | | 115-199 |
| 0110 | 20 | GA | | | 4-0 | 24-22-11 | D01728 | 41 | | | D40392J | 32 | | | 001-099 |
| 0110 | 20 | GA | | | 5-0 | 24-22-11 | D01728 | 41 | | | D40392J | 32 | | | 115-199 |
| 0111 | 24 | GK | | | 4-0 | 24-22-11 | D01728 | 3 | | | D40392J | 2 | | | 001-099 |
| 0111 | 24 | GK | | | 5-0 | 24-22-11 | D01728 | 3 | | | D40392J | 2 | | | 115-199 |
| 0112 | 24 | GK | | | 4-0 | 24-22-12 | D01728 | 7 | | | D40392J | 20 | | | 001-099 |
| 0112 | 24 | GK | | | 5-0 | 24-22-12 | D01728 | 7 | | | D40392J | 20 | | | 115-199 |
| 0113 | 24 | GK | | | 4-7 | 24-22-12 | D01728 | 22 | | | D41318J | 17 | | | 001-099 |
| 0113 | 24 | GK | | | 7-0 | 24-22-12 | D01728 | 22 | | | D41318J | 17 | | | 115-199 |
| 0114 | 24 | GK | | | 2-0 | 24-22-12 | D01730 | 7 | | | D40392J | 21 | | | 001-099 |
| 0114 | 24 | GK | | | 3-0 | 24-22-12 | D01730 | 7 | | | D40392J | 21 | | | 115-199 |
| 0115 | 24 | GK | | | 2-0 | 24-22-12 | D01730 | 3 | | | D40392J | 14 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 7

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1136 | 286N1136 | | | P31 MODULE WIRING (continued) | | | | | | | | | | | |
| 0115 | 24 | | GK | | 3-0 | 24-22-12 | D01730 | | 3 | | D40392J | 14 | | | 115-199 |
| 0116 | 20 | | GA | | 2-0 | 24-22-12 | D01730 | | 41 | | D40392J | 36 | | | 001-099 |
| 0116 | 20 | | GA | | 3-0 | 24-22-12 | D01730 | | 41 | | D40392J | 36 | | | 115-199 |
| 0117 | 24 | | GK | | 2-6 | 24-27-11 | D01730 | | 16 | | D41318J | 23 | | | 001-099 |
| 0117 | 24 | | GK | | 3-0 | 24-27-11 | D01730 | | 16 | | D41318J | 23 | | | 115-199 |
| 0118 | 24 | | GK | | 4-0 | 24-27-11 | D01728 | | 9 | | D40392J | 12 | | | 001-099 |
| 0118 | 24 | | GK | | 5-0 | 24-27-11 | D01728 | | 9 | | D40392J | 12 | | | 115-199 |
| 0119 | 24 | | GK | | 4-4 | 24-27-11 | D01728 | | 1 | | TB0131A | C013 | 2 | | 001-099 |
| 0119 | 24 | | GK | | 5-0 | 24-27-11 | D01728 | | 1 | | TB0131A | C013 | 2 | | 115-199 |
| 0120 | 24 | | GK | | 3-10 | 24-27-21 | D01728 | | 6 | | D01730 | 23 | | | 001-099 |
| 0120 | 24 | | GK | | 4-0 | 24-27-21 | D01728 | | 6 | | D01730 | 23 | | | 115-199 |
| 0121 | 24 | | GK | | 7-5 | 24-28-11 | C00818 | | =L | D | D40392J | 11 | | | 001-099 |
| 0121 | 24 | | GK | | 7-3 | 24-28-11 | C00818 | | =L | D | D40392J | 11 | | | 115-199 |
| 0122 | 18 | | GA | | 2-9 | 24-28-11 | C00818 | | =B | D | C00901 | T2 | H | * | 001-099 |
| 0122 | 18 | | GA | | 4-0 | 24-28-11 | C00818 | | =B | D | C00901 | T2 | H | * | 115-199 |
| 0123 | 24 | | GK | | 2-6 | 24-51-31 | TB0131Y | | C012 | BJ | D41318J | 19 | | | 001-099 |
| 0123 | 24 | | GK | | 3-0 | 24-51-31 | TB0131Y | | C012 | BJ | D41318J | 19 | | | 115-199 |
| 0124 | 24 | | GK | | 4-3 | 24-51-71 | D01728 | | 25 | | D40580J | 12 | | | 001-099 |
| 0124 | 24 | | GK | | 8-0 | 24-51-71 | D01728 | | 25 | | D40580J | 12 | | | 115-199 |
| 0125 | 24 | | GK | | 2-6 | 24-51-71 | D01730 | | 5 | | D41318J | 14 | | | 001-099 |
| 0125 | 24 | | GK | | 3-0 | 24-51-71 | D01730 | | 5 | | D41318J | 14 | | | 115-199 |
| 0126 | 24 | | GK | | 4-7 | 24-51-71 | D01728 | | 26 | | D41318J | 5 | | | 001-099 |
| 0126 | 24 | | GK | | 7-0 | 24-51-71 | D01728 | | 26 | | D41318J | 5 | | | 115-199 |
| 0127 | 24 | | GK | | 2-6 | 24-51-71 | D01730 | | 6 | | D41318J | 6 | | | 001-099 |
| 0127 | 24 | | GK | | 3-0 | 24-51-71 | D01730 | | 6 | | D41318J | 6 | | | 115-199 |
| 0133 | 22 | | GA | | 6-5 | 25-31-33 | D02352 | | 13 | | TB0131B | C007 | 2 | | 001-099 |
| 0134 | 16 | | GA | | 0-7 | 29-11-31 | SM00003 | | | WI | D02934 | 8 | 16 | | 001-099 |
| 0134 | 16 | | GA | | 1-0 | 29-11-31 | SM00003 | | | WI | D02934 | 8 | 16 | | 115-199 |
| 0135 | 22 | | GA | | 6-5 | 25-31-33 | D02352 | | 11 | | TB0131B | A007 | 2 | | 001-099 |
| 0135 | 22 | | GA | | 1-0 | 25-31-33 | D02352 | | 11 | | D02352 | 13 | | | 115-199 |
| 0136 | 22 | | GA | | 0-7 | 25-31-33 | D02352 | | 16 | | D02352 | 17 | | | 001-099 |
| 0136 | 22 | | GA | | 1-0 | 25-31-33 | D02352 | | 16 | | D02352 | 17 | | | 115-199 |
| 0137 | 22 | | GA | | 5-1 | 25-31-33 | D02352 | | 1 | | D40662J | 2 | | | 001-099 |
| 0137 | 22 | | GA | | 6-0 | 25-31-33 | D02352 | | 1 | | D40662J | 2 | | | 115-199 |
| 0138 | 22 | | GA | | 5-1 | 25-31-33 | D02352 | | 2 | | D40662J | 3 | | | 001-099 |
| 0138 | 22 | | GA | | 6-0 | 25-31-33 | D02352 | | 2 | | D40662J | 3 | | | 115-199 |
| 0139 | 22 | | GA | | 5-1 | 25-31-33 | D02352 | | 3 | | D40662J | 6 | | | 001-099 |
| 0139 | 22 | | GA | | 6-0 | 25-31-33 | D02352 | | 3 | | D40662J | 6 | | | 115-199 |
| 0140 | 22 | | GA | | 5-1 | 25-31-33 | D02352 | | 4 | | D40662J | 5 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 8

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1136 | 286N1136 | | | P31 MODULE WIRING (continued) | | | | | | | | | | | |
| 0140 | 22 | | GA | | 6-0 | 25-31-33 | D02352 | | 4 | | D40662J | | 5 | | 115-199 |
| 0141 | 20 | | GA | | 5-5 | 25-31-33 | D02352 | | 9 | | D40392J | | 22 | | 001-099 |
| 0141 | 20 | | GA | | 6-0 | 25-31-33 | D02352 | | 9 | | D40392J | | 22 | | 115-199 |
| 0142 | 16 | | GA | | 6-3 | 29-11-22 | SM00004 | | | WI | D40392J | | 42 | | 001-099 |
| 0142 | 16 | | GA | | 6-0 | 29-11-22 | SM00004 | | | WI | D40392J | | 42 | | 115-199 |
| 0143 | 24 | | GK | | 1-11 | 24-22-12 | D41318J | | 20 | | D40392J | | 38 | | 001-099 |
| 0143 | 24 | | GK | | 4-0 | 24-22-12 | D41318J | | 20 | | D40392J | | 38 | | 115-199 |
| 0144 | 24 | | GK | | 2-2 | 24-27-11 | D01730 | | 9 | | D40580J | | 26 | | 001-099 |
| 0144 | 24 | | GK | | 3-0 | 24-27-11 | D01730 | | 9 | | D40580J | | 26 | | 115-199 |
| 0200 | 20 | | GA | | 2-1 | 24-22-12 | GD00531 | DC.. | 2 | | D01730 | | 4 | | 001-099 |
| 0200 | 20 | | GA | | 3-0 | 24-22-12 | GD00531 | DC.. | 2 | | D01730 | | 4 | | 115-199 |
| 0201 | 20 | | GA | | 2-1 | 24-22-12 | GD00531 | DC.. | 2 | | D01730 | | 8 | | 001-099 |
| 0201 | 20 | | GA | | 3-0 | 24-22-12 | GD00531 | DC.. | 2 | | D01730 | | 8 | | 115-199 |
| 0202 | 20 | | GA | | 2-1 | 24-27-11 | GD00531 | DC.. | 2 | | D01730 | | 10 | | 001-099 |
| 0202 | 20 | | GA | | 3-0 | 24-27-11 | GD00531 | DC.. | 2 | | D01730 | | 10 | | 115-199 |
| 0203 | 20 | | GA | | 4-1 | 24-22-12 | GD00531 | DC.. | 2 | | D01728 | | 8 | | 001-099 |
| 0203 | 20 | | GA | | 5-0 | 24-22-12 | GD00531 | DC.. | 2 | | D01728 | | 8 | | 115-199 |
| 0204 | 20 | | GA | | 2-1 | 24-22-12 | GD00531 | DC.. | 2 | | D01730 | | 40 | | 001-099 |
| 0204 | 20 | | GA | | 3-0 | 24-22-12 | GD00531 | DC.. | 2 | | D01730 | | 40 | | 115-199 |
| 0205 | 20 | | GA | | 4-1 | 24-22-11 | GD00531 | DC.. | 2 | | D01728 | | 4 | | 001-099 |
| 0205 | 20 | | GA | | 5-0 | 24-22-11 | GD00531 | DC.. | 2 | | D01728 | | 4 | | 115-199 |
| 0206 | 20 | | GA | | 4-1 | 24-22-11 | GD00531 | DC.. | 2 | | D01728 | | 40 | | 001-099 |
| 0206 | 20 | | GA | | 5-0 | 24-22-11 | GD00531 | DC.. | 2 | | D01728 | | 40 | | 115-199 |
| 0207 | 20 | | GA | | 2-1 | 24-27-11 | GD00531 | DC.. | 2 | | D01730 | | 2 | | 001-099 |
| 0207 | 20 | | GA | | 3-0 | 24-27-11 | GD00531 | DC.. | 2 | | D01730 | | 2 | | 115-199 |
| 0208 | 20 | | GA | | 4-1 | 24-27-11 | GD00531 | DC.. | 2 | | D01728 | | 10 | | 001-099 |
| 0208 | 20 | | GA | | 5-0 | 24-27-11 | GD00531 | DC.. | 2 | | D01728 | | 10 | | 115-199 |
| 0300 | 20 | | GA | | 4-1 | 24-22-12 | D01728 | | 14 | | TB0131Y | A001 | BJ | | 001-099 |
| 0300 | 20 | | GA | | 6-0 | 24-22-12 | D01728 | | 14 | | TB0131Y | A001 | BJ | | 115-199 |
| 0301 | 20 | | GA | | 4-1 | 24-22-12 | D01728 | | 13 | | TB0131Y | C001 | BJ | | 001-099 |
| 0301 | 20 | | GA | | 6-0 | 24-22-12 | D01728 | | 13 | | TB0131Y | C001 | BJ | | 115-199 |
| 0302 | 24 | | GK | | 3-8 | 24-22-12 | D02182 | | A2 | | TB0131Y | C001 | BJ | | 001-099 |
| 0302 | 24 | | GK | | 5-0 | 24-22-12 | D02182 | | A2 | | TB0131Y | C001 | BJ | | 115-199 |
| 0303 | 24 | | GK | | 3-10 | 24-22-12 | D02182 | | B2 | | TB0131Y | C012 | BJ | | 001-099 |
| 0303 | 24 | | GK | | 5-0 | 24-22-12 | D02182 | | B2 | | TB0131Y | C012 | BJ | | 115-199 |
| 0304 | 24 | | GK | | 3-8 | 24-22-12 | D02182 | | X1 | | TB0131Y | A002 | BJ | | 001-099 |
| 0304 | 24 | | GK | | 5-0 | 24-22-12 | D02182 | | X1 | | TB0131Y | A002 | BJ | | 115-199 |
| 0305 | 24 | | GK | | 4-1 | 24-22-12 | D01728 | | 27 | | TB0131Y | A002 | BJ | | 001-099 |
| 0305 | 24 | | GK | | 6-0 | 24-22-12 | D01728 | | 27 | | TB0131Y | A002 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 9

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1136 | 286N1136 | | | P31 MODULE WIRING (continued) | | | | | | | | | | | |
| 0306 | 24 | | GK | | 4-1 | 24-22-12 | D01728 | | | 28 | TB0131Y | C002 | BJ | | 001-099 |
| 0306 | 24 | | GK | | 6-0 | 24-22-12 | D01728 | | | 28 | TB0131Y | C002 | BJ | | 115-199 |
| 0307 | 24 | | GK | | 2-4 | 24-22-12 | D41318J | | | 12 | TB0131Y | A002 | BJ | | 001-099 |
| 0307 | 24 | | GK | | 3-0 | 24-22-12 | D41318J | | | 12 | TB0131Y | A002 | BJ | | 115-199 |
| 0308 | 20 | | GA | | 2-4 | 24-22-12 | D41318J | | | 10 | TB0131Y | A001 | BJ | | 001-099 |
| 0308 | 20 | | GA | | 3-0 | 24-22-12 | D41318J | | | 10 | TB0131Y | A001 | BJ | | 115-199 |
| 0309 | 20 | | GA | | 2-0 | 24-22-12 | D01730 | | | 39 | TB0131Y | A001 | BJ | | ALL |
| 0310 | 24 | | GK | | 2-4 | 24-22-12 | D41318J | | | 13 | TB0131Y | C002 | BJ | | 001-099 |
| 0310 | 24 | | GK | | 3-0 | 24-22-12 | D41318J | | | 13 | TB0131Y | C002 | BJ | | 115-199 |
| 0311 | 24 | | GK | | 2-0 | 24-22-12 | D01730 | | | 25 | TB0131Y | C002 | BJ | | 001-099 |
| 0311 | 20 | | GA | | 2-0 | 24-22-12 | D01730 | | | 25 | TB0131Y | C002 | BJ | | 115-199 |
| 0312 | 20 | | GA | | 2-4 | 24-22-12 | D41318J | | | 11 | TB0131Y | C001 | BJ | | 001-099 |
| 0312 | 20 | | GA | | 3-0 | 24-22-12 | D41318J | | | 11 | TB0131Y | C001 | BJ | | 115-199 |
| 0313 | 20 | | GA | | 4-1 | 24-22-11 | D01728 | | | 37 | TB0131A | C003 | 2 | | 001-099 |
| 0313 | 20 | | GA | | 6-0 | 24-22-11 | D01728 | | | 37 | TB0131A | C003 | 2 | | 115-199 |
| 0314 | 20 | | GA | | 1-9 | 24-22-11 | D40392J | | | 33 | TB0131A | A003 | 2 | | 001-099 |
| 0314 | 20 | | GA | | 3-0 | 24-22-11 | D40392J | | | 33 | TB0131A | A003 | 2 | | 115-199 |
| 0315 | 20 | | GA | | 1-11 | 24-22-11 | D40580J | | | 24 | TB0131A | A003 | 2 | | 001-099 |
| 0315 | 20 | | GA | | 3-0 | 24-22-11 | D40580J | | | 24 | TB0131A | A003 | 2 | | 115-199 |
| 0316 | 20 | | GA | | 2-0 | 24-22-12 | D01730 | | | 37 | TB0131A | C004 | 2 | | ALL |
| 0317 | 20 | | GA | | 1-9 | 24-22-12 | D40392J | | | 35 | TB0131A | A004 | 2 | | 001-099 |
| 0317 | 20 | | GA | | 3-0 | 24-22-12 | D40392J | | | 35 | TB0131A | A004 | 2 | | 115-199 |
| 0318 | 20 | | GA | | 1-11 | 24-22-12 | D40580J | | | 9 | TB0131A | A004 | 2 | | 001-099 |
| 0318 | 20 | | GA | | 3-0 | 24-22-12 | D40580J | | | 9 | TB0131A | A004 | 2 | | 115-199 |
| 0319 | 24 | | GK | | 4-2 | 24-27-11 | D01728 | | | 2 | TB0131Y | A005 | BJ | | 001-099 |
| 0319 | 24 | | GK | | 6-0 | 24-27-11 | D01728 | | | 2 | TB0131Y | A005 | BJ | | 115-199 |
| 0320 | 24 | | GK | | 2-1 | 24-27-11 | D01730 | | | 1 | TB0131Y | A005 | BJ | | 001-099 |
| 0320 | 24 | | GK | | 2-0 | 24-27-11 | D01730 | | | 1 | TB0131Y | A005 | BJ | | 115-199 |
| 0321 | 24 | | GK | | 2-1 | 24-27-11 | D01730 | | | 15 | TB0131Y | A005 | BJ | | 001-099 |
| 0321 | 24 | | GK | | 2-0 | 24-27-11 | D01730 | | | 15 | TB0131Y | A005 | BJ | | 115-199 |
| 0322 | 24 | | GK | | 4-2 | 24-27-21 | D01728 | | | 5 | TB0131Y | C005 | BJ | | 001-099 |
| 0322 | 24 | | GK | | 6-0 | 24-27-21 | D01728 | | | 5 | TB0131Y | C005 | BJ | | 115-199 |
| 0323 | 24 | | GK | | 2-1 | 24-27-21 | D01730 | | | 21 | TB0131Y | C005 | BJ | | 001-099 |
| 0323 | 24 | | GK | | 2-0 | 24-27-21 | D01730 | | | 21 | TB0131Y | C005 | BJ | | 115-199 |
| 0324 | 24 | | GK | | 2-1 | 24-27-21 | D01730 | | | 22 | TB0131Y | A006 | BJ | | 001-099 |
| 0324 | 24 | | GK | | 2-0 | 24-27-21 | D01730 | | | 22 | TB0131Y | A006 | BJ | | 115-199 |
| 0325 | 24 | | GK | | 2-1 | 24-27-21 | D01730 | | | 24 | TB0131Y | A006 | BJ | | 001-099 |
| 0325 | 24 | | GK | | 2-0 | 24-27-21 | D01730 | | | 24 | TB0131Y | A006 | BJ | | 115-199 |
| 0326 | 24 | | GK | | 2-5 | 24-27-21 | D41318J | | | 15 | TB0131Y | C005 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 10

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1136 | | 286N1136 | | | | P31 MODULE WIRING (continued) | | | | | | | | | |
| 0326 | 24 | GK | | | 3-0 | 24-27-21 | D41318J | 15 | | | TB0131Y | C005 | BJ | | 115-199 |
| 0327 | 24 | GK | | | 2-5 | 24-27-21 | D41318J | 16 | | | TB0131Y | A006 | BJ | | 001-099 |
| 0327 | 24 | GK | | | 3-0 | 24-27-21 | D41318J | 16 | | | TB0131Y | A006 | BJ | | 115-199 |
| 0329 | 24 | GK | | | 2-10 | 24-51-31 | D02182 | B1 | | | D41318J | 18 | | | 001-099 |
| 0329 | 24 | GK | | | 4-0 | 24-51-31 | D02182 | B1 | | | D41318J | 18 | | | 115-199 |
| 0330 | 22 | GA | | | 6-9 | 29-11-22 | D03062 | 1 | | | TB0131Y | C006 | BJ | | 001-099 |
| 0330 | 22 | GA | | | 7-0 | 29-11-22 | D03062 | 1 | | | TB0131Y | C006 | BJ | | 115-199 |
| 0331 | 22 | GA | | | 6-9 | 29-11-22 | D03062 | 2 | | | TB0131Y | C006 | BJ | | 001-099 |
| 0331 | 22 | GA | | | 7-0 | 29-11-22 | D03062 | 2 | | | TB0131Y | C006 | BJ | | 115-199 |
| 0332 | 22 | GA | | | 6-9 | 29-11-22 | D03062 | 3 | | | TB0131Y | C006 | BJ | | 001-099 |
| 0332 | 22 | GA | | | 7-0 | 29-11-22 | D03062 | 3 | | | TB0131Y | C006 | BJ | | 115-199 |
| 0333 | 22 | GA | | | 6-9 | 29-11-22 | D03062 | 4 | | | TB0131Y | C006 | BJ | | 001-099 |
| 0333 | 22 | GA | | | 7-0 | 29-11-22 | D03062 | 4 | | | TB0131Y | C006 | BJ | | 115-199 |
| 0334 | 20 | GA | | | 6-10 | 29-11-22 | D03062 | 9 | | | GD02340 | DC.. | 2 | | 001-099 |
| 0334 | 20 | GA | | | 1-0 | 29-11-22 | D03062 | 9 | | | SM00009 | | WI | | 115-199 |
| 0335 | 20 | GA | | | 5-2 | 29-11-31 | D02934 | 9 | | | GD02340 | DC.. | 2 | | 001-099 |
| 0335 | 20 | GA | | | 1-0 | 29-11-31 | D02934 | 9 | | | SM00010 | | WI | | 115-199 |
| 0336 | 22 | GA | | | 5-1 | 29-11-31 | D02934 | 1 | | | TB0131Y | A011 | BJ | | 001-099 |
| 0336 | 22 | GA | | | 6-0 | 29-11-31 | D02934 | 1 | | | TB0131Y | A011 | BJ | | 115-199 |
| 0337 | 22 | GA | | | 5-1 | 29-11-31 | D02934 | 2 | | | TB0131Y | A011 | BJ | | 001-099 |
| 0337 | 22 | GA | | | 6-0 | 29-11-31 | D02934 | 2 | | | TB0131Y | A011 | BJ | | 115-199 |
| 0338 | 22 | GA | | | 5-1 | 29-11-31 | D02934 | 3 | | | TB0131Y | A011 | BJ | | 001-099 |
| 0338 | 22 | GA | | | 6-0 | 29-11-31 | D02934 | 3 | | | TB0131Y | A011 | BJ | | 115-199 |
| 0339 | 22 | GA | | | 5-1 | 29-11-31 | D02934 | 4 | | | TB0131Y | A011 | BJ | | 001-099 |
| 0339 | 22 | GA | | | 6-0 | 29-11-31 | D02934 | 4 | | | TB0131Y | A011 | BJ | | 115-199 |
| 0343 | 22 | GA | | | 1-10 | 29-11-31 | SM00002 | | WI | | D01730 | 17 | | | 001-099 |
| 0343 | 22 | GA | | | 6-0 | 29-11-31 | SM00002 | | WI | | D01730 | 17 | | | 115-199 |
| 0344 | 22 | GA | | | 1-10 | 29-11-31 | SM00001 | | WI | | D01730 | 18 | | | 001-099 |
| 0344 | 22 | GA | | | 6-0 | 29-11-31 | SM00001 | | WI | | D01730 | 18 | | | 115-199 |
| 0353 | 18 | GA | | | 6-0 | 25-31-33 | D40580J | 18 | 18 | | D02352 | 8 | 18 | | 115-199 |
| 0354 | 24 | GK | | | 2-6 | 24-22-22 | D41318J | 1 | | | D01730 | 27 | | | 001-099 |
| 0354 | 24 | GK | | | 3-0 | 24-22-22 | D41318J | 1 | | | D01730 | 27 | | | 115-199 |
| 0355 | 24 | GK | | | 2-6 | 24-22-22 | D41318J | 2 | | | D01730 | 28 | | | 001-099 |
| 0355 | 24 | GK | | | 3-0 | 24-22-22 | D41318J | 2 | | | D01730 | 28 | | | 115-199 |
| 0356 | 20 | GA | | | 4-7 | 24-22-22 | D41318J | 4 | | | D01728 | 18 | | | 001-099 |
| 0356 | 20 | GA | | | 7-0 | 24-22-22 | D41318J | 4 | | | D01728 | 18 | | | 115-199 |
| 0357 | 24 | GK | | | 4-7 | 24-22-22 | D41318J | 25 | | | D01728 | 17 | | | 001-099 |
| 0357 | 24 | GK | | | 7-0 | 24-22-22 | D41318J | 25 | | | D01728 | 17 | | | 115-199 |
| 2001B | 22 | GB | RB | | 5-0 | 29-11-22 | T00155 | X2 | E | | D40580J | 6 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 11

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1136 | 286N1136 | | | P31 MODULE WIRING (continued) | | | | | | | | | | | |
| 2001R | 22 | GB | RB | | 0-0 | 29-11-22 | T00155 | X1 | E | | D40580J | 5 | | | 115-199 |
| 2002B | 22 | GB | BR | | 5-0 | 29-11-31 | T00157 | X1 | E | | D40580J | 7 | | | 115-199 |
| 2002R | 22 | GB | BR | | 0-0 | 29-11-31 | T00157 | X2 | E | | D40580J | 8 | | | 115-199 |
| 4001B | 24 | GN | DD | | 2-0 | 24-23-11 | D02162 | | 3 | | D40392J | 4 | | | 001-099 |
| 4001B | 24 | GN | DD | | 3-0 | 24-23-11 | D02162 | | 3 | | D40392J | 4 | | | 115-199 |
| 4001G | 24 | GN | DD | | 0-0 | 24-23-11 | D02162 | | 4 | | D40392J | 3 | | | ALL |
| 4001R | 24 | GN | DD | | 0-0 | 24-23-11 | D02162 | | 1 | | D40392J | 6 | | | ALL |
| 4001Y | 24 | GN | DD | | 0-0 | 24-23-11 | D02162 | | 2 | | D40392J | 5 | | | ALL |
| 4002B | 24 | GN | EE | | 2-3 | 24-23-11 | D02166 | | 3 | | D40392J | 8 | | | 001-099 |
| 4002B | 24 | GN | EE | | 3-0 | 24-23-11 | D02166 | | 3 | | D40392J | 8 | | | 115-199 |
| 4002G | 24 | GN | EE | | 0-0 | 24-23-11 | D02166 | | 4 | | D40392J | 7 | | | ALL |
| 4002R | 24 | GN | EE | | 0-0 | 24-23-11 | D02166 | | 1 | | D40392J | 10 | | | ALL |
| 4002Y | 24 | GN | EE | | 0-0 | 24-23-11 | D02166 | | 2 | | D40392J | 9 | | | ALL |
| 4003B | 24 | GN | FF | | 2-9 | 24-23-12 | D02168 | | 3 | | D40392J | 16 | | | 001-099 |
| 4003B | 24 | GN | FF | | 4-0 | 24-23-12 | D02168 | | 3 | | D40392J | 16 | | | 115-199 |
| 4003G | 24 | GN | FF | | 0-0 | 24-23-12 | D02168 | | 4 | | D40392J | 17 | | | ALL |
| 4003R | 24 | GN | FF | | 0-0 | 24-23-12 | D02168 | | 1 | | D40392J | 18 | | | ALL |
| 4003Y | 24 | GN | FF | | 0-0 | 24-23-12 | D02168 | | 2 | | D40392J | 19 | | | ALL |
| W1138 | 286N1138 | | | P32 MODULE WIRING | | | | | | | | | | | |
| 0001 | 20 | GA | | | 3-0 | 24-22-22 | D40394J | | 42 | | TB0132Y | A001 | BJ | | ALL |
| 0002 | 20 | GA | | | 8-0 | 24-22-22 | D01816 | | 18 | | TB0132Y | A001 | BJ | | ALL |
| 0003 | 24 | GK | | | 6-0 | 24-22-22 | D01816 | | 7 | | D40394J | 19 | | | ALL |
| 0004 | 24 | GK | | | 8-0 | 24-22-22 | D01816 | | 17 | | TB0132Y | C001 | BJ | | ALL |
| 0005 | 24 | GK | | | 3-0 | 24-22-22 | D40394J | | 37 | | TB0132Y | C001 | BJ | | ALL |
| 0006 | 24 | GK | | | 8-0 | 24-22-22 | D01816 | | 27 | | TB0132Y | A002 | BJ | | ALL |
| 0007 | 24 | GK | | | 3-0 | 24-22-22 | D40394J | | 40 | | TB0132Y | A002 | BJ | | ALL |
| 0008 | 24 | GK | | | 3-0 | 24-22-22 | D40394J | | 39 | | TB0132Y | C002 | BJ | | ALL |
| 0009 | 20 | GA | | | 2-0 | 24-22-22 | D02242 | | X2 | | GD00539 | AC.. | 2 | | ALL |
| 0010 | 24 | GK | | | 2-0 | 24-22-22 | D02242 | | X1 | | TB0132Y | A002 | BJ | | ALL |
| 0011 | 24 | GK | | | 2-0 | 24-22-22 | D02242 | | B2 | | TB0132Y | C011 | BJ | | ALL |
| 0012 | 24 | GK | | | 2-0 | 24-22-22 | D02242 | | A2 | | TB0132Y | C001 | BJ | | ALL |
| 0013 | 20 | GA | | | 3-0 | 24-22-22 | D02242 | | A3 | | D40394J | 22 | | | ALL |
| 0014 | 20 | GA | | | 3-0 | 24-22-22 | TB0132A | A005 | 2 | | D40592J | 4 | | | ALL |
| 0015 | 20 | GA | | | 3-0 | 24-22-22 | TB0132A | C005 | 2 | | D01818 | 37 | | | ALL |
| 0016 | 20 | GA | | | 3-0 | 24-22-22 | GD00537 | DC.. | 2 | | D01818 | 40 | | | ALL |
| 0017 | 20 | GA | | | 3-0 | 24-22-22 | TB0132A | A005 | 2 | | D40394J | 27 | | | ALL |
| 0018 | 20 | GA | | | 3-0 | 24-22-22 | D40394J | | 15 | | D01818 | 41 | | | 001-099 |
| 0018 | 20 | GA | | | 4-0 | 24-22-22 | D40394J | | 15 | | D01818 | 41 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 12

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|-------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1138 | 286N1138 | | | P32 MODULE WIRING (continued) | | | | | | | | | | | | |
| 0019 | 20 | GA | | | 3-0 | 24-22-22 | TB0132Y | A001 | BJ | | | D01818 | 39 | | | ALL |
| 0020 | 18 | GA | | | 4-0 | 24-22-22 | C00904 | L2 | H | | | D41316J | 4 | | | ALL |
| 0021 | 24 | GK | | | 3-0 | 24-22-22 | D01818 | 7 | | | | D40394J | 20 | | | 001-099 |
| 0021 | 24 | GK | | | 4-0 | 24-22-22 | D01818 | 7 | | | | D40394J | 20 | | | 115-199 |
| 0022 | 24 | GK | | | 3-0 | 24-22-22 | D01818 | 3 | | | | D40394J | 21 | | | 001-099 |
| 0022 | 24 | GK | | | 4-0 | 24-22-22 | D01818 | 3 | | | | D40394J | 21 | | | 115-199 |
| 0023 | 18 | GA | | | 3-0 | 24-28-11 | C00903 | T2 | H | * | | C00819 | = B | D | | 001-099 |
| 0023 | 18 | GA | | | 2-0 | 24-28-11 | C00903 | T2 | H | * | | C00819 | = B | D | | 115-199 |
| 0024 | 24 | GK | | | 6-0 | 24-28-11 | D40394J | 5 | | | | C00819 | = L | D | | 001-099 |
| 0024 | 24 | GK | | | 8-0 | 24-28-11 | D40394J | 5 | | | | C00819 | = L | D | | 115-199 |
| 0025 | 20 | GA | | | 7-0 | 24-22-22 | D01816 | 8 | | | | GD00537 | DC.. | 2 | | ALL |
| 0026 | 24 | GK | | | 8-0 | 24-22-22 | D01816 | 28 | | | | TB0132Y | C002 | BJ | | ALL |
| 0027 | 24 | GK | | | 3-0 | 24-22-22 | D01818 | 25 | | | | TB0132Y | C002 | BJ | | ALL |
| 0028 | 20 | GA | | | 3-0 | 24-22-22 | D01818 | 8 | | | | GD00537 | DC.. | 2 | | ALL |
| 0029 | 20 | GA | | | 3-0 | 24-22-22 | D01818 | 4 | | | | GD00537 | DC.. | 2 | | ALL |
| 0030 | 20 | GA | | | 7-0 | 24-27-21 | D01816 | 10 | | | | GD00537 | DC.. | 2 | | ALL |
| 0031 | 24 | GK | | | 7-0 | 24-27-21 | D01816 | 1 | | | | TB0132A | C013 | 2 | | ALL |
| 0032 | 24 | GK | | | 6-0 | 24-27-21 | D01816 | 9 | | | | D40394J | 4 | | | ALL |
| 0033 | 24 | GK | | | 8-0 | 24-27-21 | D01816 | 2 | | | | TB0132Y | A003 | BJ | | ALL |
| 0034 | 24 | GK | | | 3-0 | 24-27-21 | D01818 | 1 | | | | TB0132Y | A003 | BJ | | ALL |
| 0035 | 24 | GK | | | 3-0 | 24-27-21 | D01818 | 15 | | | | TB0132Y | A003 | BJ | | ALL |
| 0036 | 20 | GA | | | 3-0 | 24-27-21 | D01818 | 2 | | | | GD00537 | DC.. | 2 | | ALL |
| 0037 | 24 | GK | | | 3-0 | 24-27-21 | D01818 | 16 | | | | D41316J | 26 | | | ALL |
| 0038 | 18 | GA | | | 5-0 | 24-21-51 | L00008 | 1 | C | | | GD00539 | AC.. | 2 | | 001-099 |
| 0038 | 18 | GA | | | 5-0 | 24-21-51 | L00008 | 1 | I | | | GD00539 | AC.. | 2 | | 115-199 |
| 0039 | 18 | GA | | | 5-0 | 24-21-51 | L00008 | 2 | C | | | C00904 | L3 | H | | 001-099 |
| 0039 | 18 | GA | | | 5-0 | 24-21-51 | L00008 | 2 | I | | | C00904 | L3 | H | | 115-199 |
| 0040 | 18 | GA | | | 5-0 | 24-22-21 | C00903 | L2 | H | | | D41316J | 8 | | | 001-099 |
| 0040 | 18 | GA | | | 4-0 | 24-22-21 | C00903 | L2 | H | | | D41316J | 8 | | | 115-199 |
| 0041 | 24 | GK | | | 6-0 | 24-22-21 | D01816 | 3 | | | | D40394J | 23 | | | ALL |
| 0042 | 20 | GA | | | 6-0 | 24-22-21 | D01816 | 39 | | | | D40394J | 24 | | | ALL |
| 0043 | 20 | GA | | | 7-0 | 24-22-21 | D01816 | 40 | | | | GD00537 | DC.. | 2 | | ALL |
| 0044 | 20 | GA | | | 6-0 | 24-22-21 | D01816 | 41 | | | | D40394J | 25 | | | ALL |
| 0045 | 20 | GA | | | 3-0 | 24-22-21 | TB0132A | A006 | 2 | | | D40592J | 2 | | | ALL |
| 0046 | 20 | GA | | | 8-0 | 24-22-21 | D01816 | 37 | | | | TB0132A | C006 | 2 | | 001-099 |
| 0046 | 20 | GA | | | 7-0 | 24-22-21 | D01816 | 37 | | | | TB0132A | C006 | 2 | | 115-199 |
| 0047 | 20 | GA | | | 7-0 | 24-22-21 | D01816 | 4 | | | | GD00537 | DC.. | 2 | | ALL |
| 0048 | 18 | GA | | | 5-0 | 24-21-21 | C00903 | T2 | H | * | | D41316J | 2 | | | ALL |
| 0049 | 18 | GA | | | 5-0 | 24-21-21 | C00903 | T3 | H | * | | D41316J | 6 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 13

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1138 | 286N1138 | | | P32 MODULE WIRING (continued) | | | | | | | | | | | |
| 0050 | 18 | | GA | | 3-0 | 24-21-21 | C00903 | T3 | H | * | L00014 | 1 | C | | 001-099 |
| 0050 | 18 | | GA | | 2-0 | 24-21-21 | C00903 | T3 | H | * | L00014 | 1 | I | | 115-199 |
| 0051 | 18 | | GA | | 5-0 | 24-21-21 | GD00539 | AC.. | 2 | | L00014 | 2 | C | | 001-099 |
| 0051 | 18 | | GA | | 5-0 | 24-21-21 | GD00539 | AC.. | 2 | | L00014 | 2 | I | | 115-199 |
| 0052 | 18 | | GA | | 4-0 | 24-21-21 | C00904 | T3 | H | | L00013 | 1 | I | | 001-099 |
| 0052 | 18 | | GA | | 5-0 | 24-21-21 | C00904 | T3 | H | | L00013 | 1 | I | | 115-199 |
| 0053 | 18 | | GA | | 5-0 | 24-21-21 | GD00539 | AC.. | 2 | | L00013 | 2 | I | | ALL |
| 0054 | 20 | | GA | | 3-0 | 24-22-21 | TB0132A | A006 | 2 | | D40592J | 3 | | | ALL |
| 0055 | 18 | | GA | | 5-0 | 24-21-21 | C00903 | T1 | H | | D41316J | 1 | | | ALL |
| 0056 | 24 | | GK | | 3-0 | 24-27-11 | D40394J | 38 | | | TB0132Y | C004 | BJ | | ALL |
| 0057 | 24 | | GK | | 3-0 | 24-27-11 | TB0132Y | C004 | BJ | | D01818 | 21 | | | ALL |
| 0058 | 24 | | GK | | 8-0 | 24-27-11 | D01816 | 6 | | | D01818 | 23 | | | ALL |
| 0059 | 24 | | GK | | 3-0 | 24-27-11 | D40394J | 41 | | | TB0132Y | A004 | BJ | | ALL |
| 0060 | 24 | | GK | | 8-0 | 24-27-11 | D01816 | 5 | | | TB0132Y | C004 | BJ | | ALL |
| 0061 | 24 | | GK | | 3-0 | 24-27-11 | D01818 | 22 | | | TB0132Y | A004 | BJ | | ALL |
| 0062 | 24 | | GK | | 3-0 | 24-27-11 | D01818 | 24 | | | TB0132Y | A004 | BJ | | ALL |
| 0065 | 22 | | GA | | 3-0 | 29-11-31 | D01818 | 17 | | | TB0132Y | A007 | BJ | | ALL |
| 0066 | 22 | | GA | | 4-0 | 29-11-31 | D01818 | 18 | | | SM00002 | | WI | | 001-099 |
| 0066 | 22 | | GA | | 5-0 | 29-11-31 | D01818 | 18 | | | SM00002 | | WI | | 115-199 |
| 0070 | 22 | | GA | | 3-0 | 29-11-31 | D40592J | 1 | | | TB0132Y | A007 | BJ | | ALL |
| 0071 | 22 | | GA | | 3-0 | 29-11-31 | D41316J | 7 | | | TB0132Y | A007 | BJ | | ALL |
| 0072 | 22 | | GA | | 3-0 | 29-11-31 | D41316J | 14 | | | SM00002 | | WI | | 001-099 |
| 0072 | 22 | | GA | | 4-0 | 29-11-31 | D41316J | 14 | | | SM00002 | | WI | | 115-199 |
| 0073 | 20 | | GA | | 5-0 | 29-11-31 | D02930 | 9 | | | GD00537 | DC.. | 2 | | 001-099 |
| 0073 | 20 | | GA | | 2-0 | 29-11-31 | D02930 | 9 | | | SM00010 | | WI | | 115-199 |
| 0074 | 16 | | GA | | 3-0 | 29-11-31 | D02930 | 8 | 16 | | SM00004 | | WI | | 001-099 |
| 0074 | 16 | | GA | | 2-0 | 29-11-31 | D02930 | 8 | 16 | | SM00004 | | WI | | 115-199 |
| 0075 | 20 | | GA | | 5-0 | 29-11-31 | D02930 | 10 | | | GD00537 | DC.. | 2 | | 001-099 |
| 0075 | 20 | | GA | | 2-0 | 29-11-31 | D02930 | 10 | | | SM00010 | | WI | | 115-199 |
| 0076 | 20 | | GA | | 5-0 | 29-11-31 | D02930 | 15 | | | GD00537 | ST.. | 2 | | ALL |
| 0077 | 22 | | GA | | 1-0 | 29-11-31 | D02930 | 11 | | | D02930 | 12 | | | ALL |
| 0078 | 22 | | GA | | 6-0 | 29-11-31 | D02930 | 1 | | | TB0132Y | A012 | BJ | | 001-099 |
| 0078 | 22 | | GA | | 5-0 | 29-11-31 | D02930 | 1 | | | TB0132Y | A012 | BJ | | 115-199 |
| 0079 | 22 | | GA | | 6-0 | 29-11-31 | D02930 | 2 | | | TB0132Y | A012 | BJ | | 001-099 |
| 0079 | 22 | | GA | | 5-0 | 29-11-31 | D02930 | 2 | | | TB0132Y | A012 | BJ | | 115-199 |
| 0080 | 22 | | GA | | 6-0 | 29-11-31 | D02930 | 3 | | | TB0132Y | A012 | BJ | | 001-099 |
| 0080 | 22 | | GA | | 5-0 | 29-11-31 | D02930 | 3 | | | TB0132Y | A012 | BJ | | 115-199 |
| 0081 | 22 | | GA | | 6-0 | 29-11-31 | D02930 | 4 | | | TB0132Y | A012 | BJ | | 001-099 |
| 0081 | 22 | | GA | | 5-0 | 29-11-31 | D02930 | 4 | | | TB0132Y | A012 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 14

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1138 | 286N1138 | | | P32 MODULE WIRING (continued) | | | | | | | | | | | |
| 0083 | 20 | | GA | | 6-0 | 29-11-12 | D03106 | 10 | | | GD00539 | DC.. | 2 | | 001-099 |
| 0083 | 20 | | GA | | 2-0 | 29-11-12 | D03106 | 10 | | | SM00009 | | WI | | 115-199 |
| 0084 | 20 | | GA | | 6-0 | 29-11-12 | D03106 | 9 | | | GD00539 | DC.. | 2 | | 001-099 |
| 0084 | 20 | | GA | | 2-0 | 29-11-12 | D03106 | 9 | | | SM00009 | | WI | | 115-199 |
| 0085 | 20 | | GA | | 6-0 | 29-11-12 | D03106 | 15 | | | GD00539 | ST.. | 2 | | ALL |
| 0086 | 16 | | GA | | 3-0 | 29-11-12 | TB0132G | 9 | 2 | | D40592J | 9 | 16 | | 001-099 |
| 0086 | 16 | | GA | | 3-0 | 29-11-12 | SM00005 | | WI | | D40592J | 9 | 16 | | 115-199 |
| 0087 | 22 | | GA | | 1-0 | 29-11-12 | D03106 | 11 | | | D03106 | 12 | | | ALL |
| 0088 | 22 | | GA | | 7-0 | 29-11-12 | D03106 | 4 | | | TB0132Y | A008 | BJ | | 001-099 |
| 0088 | 22 | | GA | | 6-0 | 29-11-12 | D03106 | 4 | | | TB0132Y | A008 | BJ | | 115-199 |
| 0089 | 22 | | GA | | 7-0 | 29-11-12 | D03106 | 3 | | | TB0132Y | A008 | BJ | | 001-099 |
| 0089 | 22 | | GA | | 6-0 | 29-11-12 | D03106 | 3 | | | TB0132Y | A008 | BJ | | 115-199 |
| 0090 | 22 | | GA | | 7-0 | 29-11-12 | D03106 | 2 | | | TB0132Y | A008 | BJ | | 001-099 |
| 0090 | 22 | | GA | | 6-0 | 29-11-12 | D03106 | 2 | | | TB0132Y | A008 | BJ | | 115-199 |
| 0091 | 22 | | GA | | 7-0 | 29-11-12 | D03106 | 1 | | | TB0132Y | A008 | BJ | | 001-099 |
| 0091 | 22 | | GA | | 6-0 | 29-11-12 | D03106 | 1 | | | TB0132Y | A008 | BJ | | 115-199 |
| 0106 | 22 | | GA | | 1-0 | 25-31-21 | D02348 | 16 | | | D02348 | 17 | | | 115-199 |
| 0107 | 22 | | GA | | 6-0 | 25-31-21 | D02348 | 1 | | | D40664J | 1 | | | 115-199 |
| 0108 | 22 | | GA | | 6-0 | 25-31-21 | D02348 | 2 | | | D40664J | 2 | | | 115-199 |
| 0109 | 22 | | GA | | 6-0 | 25-31-21 | D02348 | 3 | | | D40664J | 3 | | | 115-199 |
| 0110 | 22 | | GA | | 6-0 | 25-31-21 | D02348 | 4 | | | D40664J | 4 | | | 115-199 |
| 0111 | 22 | | GA | | 7-0 | 25-31-21 | D02348 | 11 | | | TB0132B | A014 | 2 | | 115-199 |
| 0112 | 20 | | GA | | 3-0 | 25-31-21 | D40394J | 33 | | | TB0132Y | C008 | BJ | | 115-199 |
| 0113 | 20 | | GA | | 7-0 | 25-31-21 | D02348 | 8 | | | TB0132Y | C008 | BJ | | 115-199 |
| 0114 | 20 | | GA | | 7-0 | 25-31-21 | GD00537 | DC.. | 2 | | D02348 | 10 | | | 115-199 |
| 0115 | 22 | | GA | | 2-0 | 33-27-21 | D40394J | 50 | | | D40664J | 9 | | | 115-199 |
| 0116 | 22 | | GA | | 2-0 | 33-27-21 | D40394J | 49 | | | D40664J | 10 | | | 115-199 |
| 0117 | 20 | | GA | | 2-0 | 33-27-21 | D40394J | 48 | | | D40664J | 17 | | | 115-199 |
| 0118 | 22 | | GA | | 2-0 | 33-27-11 | D40394J | 54 | | | D40664J | 15 | | | 115-199 |
| 0119 | 22 | | GA | | 2-0 | 33-27-11 | D40394J | 53 | | | D40664J | 12 | | | 115-199 |
| 0120 | 22 | | GA | | 2-0 | 33-27-11 | D40394J | 52 | | | D40664J | 11 | | | 115-199 |
| 0121 | 22 | | GA | | 2-0 | 33-27-11 | D40394J | 51 | | | D40664J | 4 | | | 001-099 |
| 0121 | 22 | | GA | | 2-0 | 33-27-11 | D40394J | 51 | | | D40664J | 13 | | | 115-199 |
| 0122 | 20 | | GA | | 5-0 | 25-31-21 | D02348 | 9 | | | D40394J | 47 | | | 115-199 |
| 0123 | 24 | | GK | | 6-0 | 24-51-71 | D01816 | 25 | | | D40592J | 5 | | | ALL |
| 0125 | 24 | | GK | | 6-0 | 24-51-71 | D01816 | 26 | | | D40394J | 30 | | | ALL |
| 0126 | 24 | | GK | | 3-0 | 24-51-71 | D01818 | 6 | | | D40394J | 31 | | | 001-099 |
| 0126 | 24 | | GK | | 4-0 | 24-51-71 | D01818 | 6 | | | D40394J | 31 | | | 115-199 |
| 0129 | 24 | | GK | | 3-0 | 24-27-21 | D01818 | 9 | | | D40592J | 17 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 15

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1138 | 286N1138 | | | | P32 MODULE WIRING (continued) | | | | | | | | | | | |
| 0130 | 20 | | GA | | 3-0 | 24-27-21 | | D01818 | 10 | | | GD00537 | DC.. | 2 | | ALL |
| 0131 | 24 | | GK | | 2-0 | 24-51-31 | | D02242 | B1 | | | TB0132Y | C012 | BJ | | ALL |
| 0132 | 24 | | GK | | 3-0 | 24-51-31 | | D41320J | 4 | | | TB0132Y | C012 | BJ | | 001-099 |
| 0132 | 24 | | GK | | 2-0 | 24-51-31 | | D41320J | 4 | | | TB0132Y | C012 | BJ | | 115-199 |
| 0133 | 24 | | GK | | 3-0 | 24-51-31 | | D41320J | 5 | | | TB0132Y | C011 | BJ | | 001-099 |
| 0133 | 24 | | GK | | 2-0 | 24-51-31 | | D41320J | 5 | | | TB0132Y | C011 | BJ | | 115-199 |
| 0134 | 24 | | GK | | 3-0 | 24-51-31 | | D40394J | 28 | | | TB0132Y | C012 | BJ | | ALL |
| 0135 | 24 | | GK | | 3-0 | 24-51-31 | | D40394J | 29 | | | TB0132Y | C011 | BJ | | ALL |
| 0136 | 24 | | GK | | 3-0 | 24-51-31 | | D01818 | 26 | | | TB0132Y | C011 | BJ | | ALL |
| 0137 | 24 | | GK | | 7-0 | 24-22-12 | | D41316J | 9 | | | D01816 | 22 | | | ALL |
| 0138 | 20 | | GA | | 7-0 | 24-22-12 | | D41316J | 28 | | | D01816 | 14 | | | ALL |
| 0139 | 20 | | GA | | 7-0 | 24-22-12 | | D41316J | 12 | | | D01816 | 13 | | | ALL |
| 0140 | 24 | | GK | | 7-0 | 24-22-12 | | D41316J | 13 | | | D01816 | 21 | | | ALL |
| 0141 | 24 | | GK | | 3-0 | 24-22-12 | | D41316J | 30 | | | D01818 | 28 | | | ALL |
| 0142 | 24 | | GK | | 3-0 | 24-22-12 | | D41316J | 11 | | | D01818 | 27 | | | ALL |
| 0144 | 22 | | GA | | 7-0 | 25-31-21 | | D02348 | 12 | | | TB0132B | C014 | 2 | | 115-199 |
| 0145 | 24 | | GK | | 3-0 | 24-51-71 | | D40394J | 2 | | | D01818 | 5 | | | 001-099 |
| 0145 | 24 | | GK | | 4-0 | 24-51-71 | | D40394J | 2 | | | D01818 | 5 | | | 115-199 |
| 0148 | 22 | | GA | | 2-0 | 29-11-31 | | D40592J | 16 | | | SM00002 | | WI | | 001-099 |
| 0148 | 22 | | GA | | 3-0 | 29-11-31 | | D40592J | 16 | | | SM00002 | | WI | | 115-199 |
| 0151 | 16 | | GA | | 7-0 | 29-11-12 | | D03106 | 8 | 16 | | TB0132G | 9 | 2 | | 001-099 |
| 0151 | 16 | | GA | | 2-0 | 29-11-12 | | D03106 | 8 | 16 | | SM00005 | | WI | | 115-199 |
| 0152 | 16 | | GA | | 7-0 | 29-11-12 | | D03106 | 18 | 16 | | TB0132G | 9 | 2 | | 001-099 |
| 0152 | 16 | | GA | | 2-0 | 29-11-12 | | D03106 | 18 | 16 | | SM00005 | | WI | | 115-199 |
| 0153 | 16 | | GA | | 2-0 | 29-11-31 | | D40592J | 15 | 16 | | SM00004 | | WI | | 001-099 |
| 0153 | 16 | | GA | | 3-0 | 29-11-31 | | D40592J | 15 | 16 | | SM00004 | | WI | | 115-199 |
| 0154 | 16 | | GA | | 3-0 | 29-11-31 | | D02930 | 18 | 16 | | SM00004 | | WI | | 001-099 |
| 0154 | 16 | | GA | | 2-0 | 29-11-31 | | D02930 | 18 | 16 | | SM00004 | | WI | | 115-199 |
| 0155 | 22 | | GA | | 3-0 | 29-11-31 | | D02242 | C2 | | | D40394J | 43 | | | ALL |
| 0156 | 22 | | GA | | 3-0 | 29-11-31 | | D02242 | C3 | | | D40592J | 10 | | | ALL |
| 0157 | 20 | | GA | | 4-0 | 29-11-12 | | SM00009 | | WI | | TB0132X | B009 | BJ | | 115-199 |
| 0158 | 20 | | GA | | 4-0 | 29-11-31 | | SM00010 | | WI | | TB0132X | A009 | BJ | | 115-199 |
| 0165 | 20 | | GA | | 7-0 | 25-31-11 | | D05236 | 10 | | | GD00537 | DC.. | 2 | | 001-099 |
| 0166 | 20 | | GA | | 5-0 | 25-31-11 | | D05236 | 9 | | | D40394J | 36 | | | 001-099 |
| 0167 | 22 | | GA | | 2-0 | 25-31-11 | | D05236 | 16 | | | D05236 | 17 | | | 001-099 |
| 0168 | 22 | | GA | | 6-0 | 25-31-11 | | D05236 | 1 | | | D40664J | 1 | | | 001-099 |
| 0169 | 22 | | GA | | 6-0 | 25-31-11 | | D05236 | 2 | | | D40664J | 2 | | | 001-099 |
| 0170 | 22 | | GA | | 6-0 | 25-31-11 | | D05236 | 3 | | | D40664J | 3 | | | 001-099 |
| 0171 | 22 | | GA | | 6-0 | 25-31-11 | | D05236 | 4 | | | D40664J | 7 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 16

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1138 | 286N1138 | | | P32 MODULE WIRING (continued) | | | | | | | | | | | |
| 0172 | 22 | | GA | | 7-0 | 25-31-11 | D05236 | | 11 | | TB0132B | A016 | 2 | | 001-099 |
| 0173 | 22 | | GA | | 7-0 | 25-31-11 | D05236 | | 12 | | TB0132B | C016 | 2 | | 001-099 |
| 0174 | 20 | | GA | | 5-0 | 25-31-11 | D40394J | | 45 | | D05236 | | 8 | | 001-099 |
| 0188 | 24 | | GK | | 3-0 | 24-27-21 | TB0132A | | C013 | 2 | D40394J | | 3 | | ALL |
| 0189 | 24 | | GK | | 3-0 | 24-27-21 | TB0132A | | A013 | 2 | D40394J | | 34 | | ALL |
| 2001B | 22 | | GB | BR | 4-0 | 29-11-12 | D40592J | | 7 | | T00156 | X1 | E | | 115-199 |
| 2001R | 22 | | GB | BR | 0-0 | 29-11-12 | D40592J | | 8 | | T00156 | X2 | E | | 115-199 |
| 4001B | 24 | | GN | AA | 4-0 | 24-23-12 | D02232 | | 3 | | D40394J | | 6 | | ALL |
| 4001G | 24 | | GN | AA | 0-0 | 24-23-12 | D02232 | | 4 | | D40394J | | 7 | | ALL |
| 4001R | 24 | | GN | AA | 0-0 | 24-23-12 | D02232 | | 1 | | D40394J | | 8 | | ALL |
| 4001Y | 24 | | GN | AA | 0-0 | 24-23-12 | D02232 | | 2 | | D40394J | | 9 | | ALL |
| 4002B | 24 | | GN | AB | 2-0 | 24-23-11 | D40394J | | 11 | | D02224 | | 3 | | ALL |
| 4002G | 24 | | GN | AB | 0-0 | 24-23-11 | D40394J | | 10 | | D02224 | | 4 | | ALL |
| 4002R | 24 | | GN | AB | 0-0 | 24-23-11 | D40394J | | 13 | | D02224 | | 1 | | ALL |
| 4002Y | 24 | | GN | AB | 0-0 | 24-23-11 | D40394J | | 12 | | D02224 | | 2 | | ALL |
| 4003B | 24 | | GN | AC | 4-0 | 24-23-11 | D40394J | | 16 | | D02230 | | 3 | | ALL |
| 4003G | 24 | | GN | AC | 0-0 | 24-23-11 | D40394J | | 14 | | D02230 | | 4 | | ALL |
| 4003R | 24 | | GN | AC | 0-0 | 24-23-11 | D40394J | | 18 | | D02230 | | 1 | | ALL |
| 4003Y | 24 | | GN | AC | 0-0 | 24-23-11 | D40394J | | 17 | | D02230 | | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1130

Page 17 End

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|---------------------------|----------|---------|---------|------|--------|-------|------|---------|--------|----|-------------|---------|
| | GA | CO TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1140 | 286N1140 | | | P50 ELECTRICAL CARD FILE. | | | | | | | | | | | | |
| 0015 | 24 | GK | | 5-0 | 22-32-13 | | D03058 | | 2 | | | D41477J | 26 | | | ALL |
| 0016 | 24 | GK | | 5-0 | 22-32-13 | | D03058 | | 10 | | | D41477J | 27 | | | ALL |
| 0017 | 24 | GK | | 5-0 | 22-32-13 | | D03058 | | 38 | | | D41477J | 28 | | | ALL |
| 0018 | 24 | GK | | 5-0 | 22-32-13 | | D03058 | | 4 | | | D41477J | 29 | | | ALL |
| 0019 | 24 | GK | | 2-0 | 22-32-13 | | D02998 | | 38 | | | D41477J | 30 | | | ALL |
| 0020 | 24 | GK | | 2-0 | 22-32-13 | | D02998 | | 48 | | | D41477J | 33 | | | ALL |
| 0021 | 24 | GK | | 2-0 | 22-32-13 | | D02998 | | 2 | | | D41477J | 34 | | | ALL |
| 0022 | 24 | GK | | 2-0 | 22-32-13 | | D02998 | | 10 | | | D41477J | 35 | | | ALL |
| 0023 | 24 | GK | | 2-0 | 22-32-13 | | D02998 | | 18 | | | D41477J | 31 | | | ALL |
| 0024 | 24 | GK | | 2-0 | 22-32-13 | | D02998 | | 4 | | | D41477J | 32 | | | ALL |
| 0025 | 22 | GA | | 4-0 | 21-51-11 | | TB0147Y | C009 | BJ | | | D40810J | 7 | | | ALL |
| 0026 | 22 | GA | | 3-0 | 21-51-11 | | D02988 | | 41 | | | GD00209 | DC.. | 2 | | ALL |
| 0027 | 22 | GA | | 3-0 | 21-51-11 | | D02988 | | 21 | | | GD00209 | DC.. | 2 | | ALL |
| 0028 | 24 | GK | | 2-0 | 21-51-11 | | D02988 | | 31 | | | D40972J | 11 | | | ALL |
| 0029 | 22 | GA | | 3-0 | 21-51-11 | | TB0147Y | C009 | BJ | | | D02988 | 19 | | | ALL |
| 0030 | 24 | GK | | 3-0 | 21-51-11 | | TB0147Y | C009 | BJ | | | D02988 | 39 | | | ALL |
| 0031 | 24 | GK | | 4-0 | 21-51-21 | | D03046 | | 36 | | | TB0147Y | C013 | BJ | | ALL |
| 0032 | 24 | GK | | 3-0 | 21-51-11 | | D03046 | | 15 | | | TB0147Y | A009 | BJ | | ALL |
| 0033 | 24 | GK | | 3-0 | 21-51-11 | | D02988 | | 36 | | | TB0147Y | A009 | BJ | | ALL |
| 0034 | 24 | GK | | 3-0 | 21-51-11 | | D02988 | | 32 | | | SM00005 | | WI | | ALL |
| 0035 | 24 | GK | | 3-0 | 21-51-11 | | D02988 | | 27 | | | GD00209 | DC.. | 2 | | ALL |
| 0038 | 24 | GK | | 3-0 | 21-51-11 | | D02988 | | 2 | | | D40972J | 29 | | | 001-099 |
| 0038 | 24 | GK | | 3-0 | 21-51-11 | | D02988 | | 2 | | | D40976J | 24 | | | 115-199 |
| 0042 | 24 | GK | | 4-0 | 21-51-11 | | TB0147Y | A009 | BJ | | | D40974J | 4 | | | ALL |
| 0043 | 22 | GA | | 2-0 | 21-51-11 | | D02988 | | 7 | | | D40974J | 3 | | | ALL |
| 0044 | 22 | GA | | 2-0 | 21-51-11 | | D02988 | | 8 | | | D40974J | 2 | | | ALL |
| 0045 | 22 | GA | | 2-0 | 21-51-11 | | D02988 | | 14 | | | D40974J | 1 | | | ALL |
| 0046 | 24 | GK | | 2-0 | 21-51-11 | | D40972J | | 5 | | | D02988 | 22 | | | ALL |
| 0047 | 24 | GK | | 3-0 | 21-51-11 | | D02988 | | 5 | | | D02838 | 15 | | | ALL |
| 0048 | 24 | GK | | 3-0 | 21-51-11 | | D02988 | | 4 | | | D02838 | 48 | | | ALL |
| 0049 | 24 | GK | | 1-0 | 21-51-11 | | D02988 | | 18 | | | D02998 | 36 | | | ALL |
| 0050 | 22 | GA | | 3-0 | 27-48-21 | | D00823 | | 7 | | | D40812J | 4 | | | ALL |
| 0051 | 22 | GA | | 3-0 | 27-48-21 | | D00823 | | 8 | | | GD00207 | AC.. | 2 | | ALL |
| 0052 | 22 | GA | | 3-0 | 27-48-21 | | D00823 | | 43 | | | GD00207 | DC.. | 2 | | ALL |
| 0055 | 22 | GA | | 3-0 | 27-48-21 | | D00821 | | 8 | | | GD00210 | AC.. | 2 | | ALL |
| 0056 | 22 | GA | | 3-0 | 27-48-21 | | D00821 | | 43 | | | GD00210 | DC.. | 2 | | ALL |
| 0058 | 22 | GA | | 3-0 | 27-48-21 | | D00909 | | 7 | | | D40810J | 5 | | | ALL |
| 0059 | 22 | GA | | 3-0 | 27-48-21 | | D00909 | | 8 | | | GD00209 | AC.. | 2 | | ALL |
| 0060 | 22 | GA | | 3-0 | 27-48-21 | | D00909 | | 43 | | | GD00209 | DC.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|---------------------------------------|-------------|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1140 | 286N1140 | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | | | | |
| 0067 | 24 | | GK | | 4-0 | 34-61-13 | D03058 | | 43 | | | D41477J | | 5 | | ALL |
| 0068 | 24 | | GK | | 4-0 | 34-61-13 | D03058 | | 42 | | | D41477J | | 6 | | ALL |
| 0069 | 24 | | GK | | 4-0 | 34-61-13 | D03058 | | 27 | | | D41477J | | 7 | | ALL |
| 0070 | 24 | | GK | | 4-0 | 34-61-13 | D03058 | | 40 | | | D41477J | | 8 | | ALL |
| 0071 | 24 | | GK | | 4-0 | 34-61-13 | D03058 | | 47 | | | D41477J | | 9 | | ALL |
| 0072 | 24 | | GK | | 4-0 | 34-61-13 | D03058 | | 16 | | | D41477J | | 43 | | ALL |
| 0073 | 24 | | GK | | 2-0 | 34-61-13 | D02998 | | 43 | | | D41477J | | 11 | | ALL |
| 0074 | 24 | | GK | | 2-0 | 34-61-13 | D02998 | | 42 | | | D41477J | | 12 | | ALL |
| 0075 | 24 | | GK | | 2-0 | 34-61-13 | D02998 | | 40 | | | D41477J | | 13 | | ALL |
| 0076 | 24 | | GK | | 2-0 | 34-61-13 | D02998 | | 16 | | | D41477J | | 44 | | ALL |
| 0077 | 24 | | GK | | 4-0 | 21-51-23 | D03046 | | 9 | | | D40976J | | 13 | | ALL |
| 0078 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 4 | | | D40976J | | 14 | | ALL |
| 0079 | 22 | | GA | | 3-0 | 21-51-23 | D03044 | | 19 | | | TB0147Y | A007 | BJ | | 001-099 |
| 0079 | 22 | | GK | | 3-0 | 21-51-23 | D03044 | | 19 | | | TB0147Y | A007 | BJ | | 115-199 |
| 0080 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 18 | | | D40976J | | 20 | | ALL |
| 0081 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 17 | | | D40976J | | 9 | | ALL |
| 0082 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 16 | | | D40976J | | 11 | | ALL |
| 0083 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 15 | | | D40976J | | 10 | | ALL |
| 0084 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 7 | | | D40976J | | 16 | | ALL |
| 0085 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 9 | | | D40976J | | 19 | | ALL |
| 0086 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 10 | | | D40976J | | 15 | | ALL |
| 0087 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 11 | | | D40976J | | 17 | | ALL |
| 0088 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 12 | | | D40976J | | 18 | | ALL |
| 0089 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 13 | | | D40976J | | 8 | | ALL |
| 0090 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 14 | | | D40976J | | 12 | | ALL |
| 0091 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 6 | | | D40972J | | 1 | | ALL |
| 0092 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 37 | | | D40972J | | 13 | | ALL |
| 0093 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 36 | | | D40972J | | 3 | | ALL |
| 0094 | 24 | | GK | | 4-0 | 21-51-23 | D03044 | | 35 | | | D40972J | | 4 | | ALL |
| 0096 | 24 | | GK | | 1-0 | 21-51-23 | D03044 | | 8 | | | D03046 | | 26 | | ALL |
| 0098 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 39 | | | TB0147Y | A003 | BJ | | ALL |
| 0099 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 17 | | | D40974J | | 19 | | ALL |
| 0100 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 18 | | | D40974J | | 38 | | ALL |
| 0101 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 13 | | | D40974J | | 40 | | ALL |
| 0102 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 15 | | | D40974J | | 16 | | ALL |
| 0103 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 16 | | | D40974J | | 17 | | ALL |
| 0104 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 14 | | | D40974J | | 18 | | ALL |
| 0105 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 5 | | | D40974J | | 41 | | ALL |
| 0106 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | 4 | | | D40974J | | 8 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 2

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1140 | 286N1140 | | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | | | | |
| 0107 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | | 10 | | | D40974J | 9 | | ALL | |
| 0108 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | | 7 | | | D40974J | 6 | | ALL | |
| 0109 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | | 11 | | | D40974J | 7 | | ALL | |
| 0110 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | | 12 | | | D40974J | 10 | | ALL | |
| 0111 | 24 | | GK | | 2-0 | 21-51-13 | D02982 | | | 9 | | | D40974J | 11 | | ALL | |
| 0112 | 24 | | GK | | 3-0 | 21-51-13 | D02982 | | | 6 | | | D40970J | 1 | | ALL | |
| 0113 | 24 | | GK | | 3-0 | 21-51-13 | D02982 | | | 37 | | | D40970J | 2 | | ALL | |
| 0114 | 24 | | GK | | 3-0 | 21-51-13 | D02982 | | | 36 | | | D40970J | 3 | | ALL | |
| 0115 | 24 | | GK | | 3-0 | 21-51-13 | D02982 | | | 35 | | | D40970J | 4 | | ALL | |
| 0116 | 24 | | GK | | 3-0 | 21-51-13 | D02982 | | | 21 | | | GD00209 | DC.. | 2 | ALL | |
| 0117 | 24 | | GK | | 1-0 | 21-51-13 | D02982 | | | 8 | | | D02988 | 26 | | ALL | |
| 0118 | 24 | | GK | | 2-0 | 21-51-15 | D02988 | | | 1 | | | D40972J | 6 | | ALL | |
| 0119 | 24 | | GK | | 2-0 | 21-51-15 | D02988 | | | 28 | | | TB0147Y | C003 | BJ | ALL | |
| 0120 | 24 | | GK | | 2-0 | 21-51-15 | D02988 | | | 10 | | | TB0147Y | C007 | BJ | ALL | |
| 0121 | 24 | | GK | | 2-0 | 21-51-15 | D02988 | | | 38 | | | TB0147Y | C008 | BJ | ALL | |
| 0122 | 24 | | GK | | 4-0 | 21-51-15 | D40974J | | | 23 | | | TB0147Y | C008 | BJ | ALL | |
| 0123 | 22 | | GA | | 3-0 | 28-21-21 | D02514 | | | 6 | | | D40970J | 13 | | ALL | |
| 0124 | 22 | | GA | | 3-0 | 28-21-21 | D02514 | | | 19 | | | D40812J | 8 | | ALL | |
| 0125 | 22 | | GA | | 3-0 | 28-21-21 | D02514 | | | 3 | | | D40812J | 7 | | ALL | |
| 0126 | 22 | | GA | | 3-0 | 28-21-21 | D02514 | | | 18 | | | GD00207 | DC.. | 2 | ALL | |
| 0127 | 24 | | GK | | 3-0 | 21-51-13 | D02982 | | | 19 | | | TB0147Y | A003 | BJ | ALL | |
| 0129 | 22 | | GA | | 4-0 | 21-51-21 | TB0147Y | | A011 | BJ | | | D40812J | 9 | | 001-099 | |
| 0129 | 22 | | GA | | 3-0 | 21-51-21 | TB0147Y | | A011 | BJ | | | D40812J | 9 | | 115-199 | |
| 0130 | 22 | | GA | | 3-0 | 21-51-21 | D03046 | | | 41 | | | GD00208 | DC.. | 2 | ALL | |
| 0131 | 22 | | GA | | 3-0 | 21-51-21 | D03046 | | | 21 | | | GD00208 | DC.. | 2 | ALL | |
| 0132 | 24 | | GK | | 3-0 | 21-51-21 | D03046 | | | 22 | | | D40970J | 10 | | ALL | |
| 0133 | 24 | | GK | | 3-0 | 21-51-21 | D03046 | | | 39 | | | TB0147Y | A011 | BJ | ALL | |
| 0134 | 24 | | GK | | 4-0 | 21-51-21 | D03046 | | | 7 | | | D40976J | 3 | | ALL | |
| 0135 | 24 | | GK | | 4-0 | 21-51-21 | D03046 | | | 8 | | | D40976J | 2 | | ALL | |
| 0136 | 24 | | GK | | 4-0 | 21-51-21 | D03046 | | | 31 | | | D40976J | 26 | | ALL | |
| 0137 | 24 | | GK | | 4-0 | 21-51-21 | TB0147Y | | A017 | BJ | | | D03058 | 35 | | 001-099 | |
| 0137 | 24 | | GK | | 3-0 | 21-51-21 | TB0147Y | | A017 | BJ | | | D03058 | 35 | | 115-199 | |
| 0138 | 24 | | GK | | 3-0 | 21-51-21 | D03046 | | | 19 | | | TB0147Y | A011 | BJ | ALL | |
| 0139 | 22 | | GA | | 3-0 | 21-51-21 | D03046 | | | 27 | | | GD00208 | DC.. | 2 | ALL | |
| 0140 | 24 | | GK | | 4-0 | 21-51-21 | D03046 | | | 14 | | | D40976J | 1 | | ALL | |
| 0142 | 24 | | GK | | 4-0 | 21-51-21 | D03046 | | | 2 | | | D40976J | 27 | | ALL | |
| 0144 | 24 | | GK | | 3-0 | 21-51-21 | D03046 | | | 4 | | | D02996 | 48 | | ALL | |
| 0145 | 24 | | GK | | 3-0 | 21-51-21 | D03046 | | | 5 | | | D02996 | 15 | | ALL | |
| 0147 | 24 | | GK | | 3-0 | 21-51-15 | D02988 | | | 17 | | | D40974J | 32 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 3

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1140 | | 286N1140 | | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | |
| 0148 | 24 | GK | | | 1-0 | 21-51-21 | D03046 | 18 | | | D03058 | 36 | | | ALL |
| 0149 | 24 | GK | | | 4-0 | 21-51-24 | D03044 | 24 | | | D40976J | 4 | | | ALL |
| 0150 | 24 | GK | | | 3-0 | 21-51-25 | D03046 | 1 | | | D40970J | 14 | | | ALL |
| 0151 | 24 | GK | | | 4-0 | 21-51-25 | D03046 | 17 | | | D40976J | 38 | | | ALL |
| 0152 | 24 | GK | | | 3-0 | 21-51-25 | D03046 | 28 | | | TB0147Y | C011 | BJ | | ALL |
| 0153 | 24 | GK | | | 4-0 | 21-51-25 | TB0147Y | C011 | BJ | | D40970J | 17 | | | 001-099 |
| 0153 | 24 | GK | | | 3-0 | 21-51-25 | TB0147Y | C011 | BJ | | D40970J | 17 | | | 115-199 |
| 0177 | 24 | GK | | | 3-0 | 36-11-21 | D02988 | 16 | | | TB0147Z | 5 | BJ | | ALL |
| 0178 | 24 | GK | | | 3-0 | 36-11-21 | D03046 | 37 | | | TB0147Z | 5 | BJ | | ALL |
| 0179 | 24 | GK | | | 4-0 | 36-11-21 | D40970J | 21 | | | TB0147Z | 5 | BJ | | 001-099 |
| 0179 | 24 | GK | | | 3-0 | 36-11-21 | D40970J | 21 | | | TB0147Z | 5 | BJ | | 115-199 |
| 0181 | 22 | GA | | | 3-0 | 36-11-11 | D02998 | 64 | | | GD00209 | DC.. | 2 | | ALL |
| 0182 | 22 | GA | | | 3-0 | 36-11-11 | D02998 | 30 | | | D40974J | 31 | | | ALL |
| 0183 | 24 | GK | | | 3-0 | 36-11-11 | D02998 | 39 | | | TB0147Z | 15 | BJ | | ALL |
| 0184 | 24 | GK | | | 3-0 | 36-11-11 | D02998 | 55 | | | TB0147Z | 15 | BJ | | ALL |
| 0185 | 24 | GK | | | 3-0 | 36-11-11 | D02988 | 37 | | | TB0147Z | 15 | BJ | | ALL |
| 0186 | 24 | GK | | | 4-0 | 36-11-11 | D03046 | 16 | | | TB0147Z | 15 | BJ | | 001-099 |
| 0186 | 24 | GK | | | 3-0 | 36-11-11 | D03046 | 16 | | | TB0147Z | 15 | BJ | | 115-199 |
| 0187 | 24 | GK | | | 4-0 | 36-11-11 | D40974J | 20 | | | TB0147Z | 15 | BJ | | ALL |
| 0188 | 24 | GK | | | 3-0 | 36-11-31 | D02998 | 61 | | | TB0147Y | A008 | BJ | | ALL |
| 0189 | 24 | GK | | | 4-0 | 36-11-31 | D03058 | 61 | | | TB0147Y | A008 | BJ | | 001-099 |
| 0189 | 24 | GK | | | 3-0 | 36-11-31 | D03058 | 61 | | | TB0147Y | A008 | BJ | | 115-199 |
| 0190 | 24 | GK | | | 4-0 | 36-11-31 | D40970J | 5 | | | TB0147Y | A008 | BJ | | 001-099 |
| 0190 | 24 | GK | | | 3-0 | 36-11-31 | D40970J | 5 | | | TB0147Y | A008 | BJ | | 115-199 |
| 0204 | 22 | GA | | | 3-0 | 73-21-22 | D03058 | 66 | | | GD00207 | DC.. | 2 | | 001-099 |
| 0204 | 22 | GK | | | 3-0 | 73-21-22 | D03058 | 66 | | | GD00207 | DC.. | 2 | | 115-199 |
| 0205 | 24 | GK | | | 3-0 | 36-11-21 | D03058 | 39 | | | TB0147Z | 5 | BJ | | ALL |
| 0207 | 22 | GA | | | 3-0 | 36-11-21 | D03058 | 64 | | | GD00207 | DC.. | 2 | | ALL |
| 0208 | 22 | GA | | | 4-0 | 36-11-21 | D03058 | 30 | | | D40970J | 39 | | | ALL |
| 0209 | 24 | GK | | | 3-0 | 36-11-21 | D03058 | 55 | | | TB0147Z | 5 | BJ | | ALL |
| 0212 | 24 | GK | | | 1-0 | 21-51-13 | D02982 | 3 | | | D02988 | 30 | | | ALL |
| 0213 | 24 | GK | | | 1-0 | 21-51-23 | D03044 | 3 | | | D03046 | 30 | | | ALL |
| 0214 | 24 | GK | | | 3-0 | 80-11-11 | D02996 | 18 | | | GD00210 | DC.. | 2 | | 001-099 |
| 0214 | 22 | GA | | | 3-0 | 80-11-11 | D02996 | 18 | | | GD00210 | DC.. | 2 | | 115-199 |
| 0215 | 24 | GK | | | 3-0 | 80-11-11 | D02996 | 49 | | | D42004J | 3 | | | ALL |
| 0218 | 24 | GK | | | 3-0 | 80-11-21 | D02838 | 20 | | | GD00210 | DC.. | 2 | | 001-099 |
| 0218 | 22 | GA | | | 3-0 | 80-11-21 | D02838 | 20 | | | GD00210 | DC.. | 2 | | 115-199 |
| 0219 | 24 | GK | | | 3-0 | 80-11-21 | D02838 | 21 | | | D41990J | 7 | | | ALL |
| 0222 | 24 | GK | | | 4-0 | 26-15-11 | D41380J | 7 | | | D42002J | 12 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 4

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1140 | 286N1140 | | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | | | | |
| 0223 | 24 | | GK | | 4-0 | 21-51-25 | TB0147Y | C011 | BJ | | | D40970J | 15 | | | 001-099 | |
| 0223 | 24 | | GK | | 3-0 | 21-51-25 | TB0147Y | C011 | BJ | | | D40970J | 15 | | | 115-199 | |
| 0225 | 24 | | GK | | 4-0 | 21-51-25 | TB0147Y | A012 | BJ | | | D40970J | 16 | | | 001-099 | |
| 0225 | 24 | | GK | | 3-0 | 21-51-25 | TB0147Y | A012 | BJ | | | D40970J | 16 | | | 115-199 | |
| 0226 | 24 | | GK | | 4-0 | 21-51-25 | D40970J | 18 | | | | TB0147Y | A012 | BJ | | ALL | |
| 0227 | 24 | | GK | | 2-0 | 21-51-25 | D40976J | 41 | | | | TB0147Y | C011 | BJ | | ALL | |
| 0228 | 24 | | GK | | 2-0 | 21-51-25 | D40976J | 7 | | | | TB0147Y | C012 | BJ | | ALL | |
| 0229 | 24 | | GK | | 3-0 | 21-51-25 | TB0147Y | A012 | BJ | | | D03046 | 10 | | | ALL | |
| 0230 | 24 | | GK | | 3-0 | 21-51-25 | D03046 | 38 | | | | TB0147Y | C012 | BJ | | ALL | |
| 0231 | 24 | | GK | | 2-0 | 21-51-25 | TB0147Y | C012 | BJ | | | D40976J | 39 | | | ALL | |
| 0232 | 24 | | GK | | 4-0 | 21-51-15 | TB0147Y | C003 | BJ | | | D40972J | 10 | | | ALL | |
| 0234 | 24 | | GK | | 4-0 | 21-51-15 | TB0147Y | C003 | BJ | | | D40972J | 7 | | | ALL | |
| 0236 | 24 | | GK | | 4-0 | 21-51-15 | TB0147Y | C007 | BJ | | | D40972J | 8 | | | ALL | |
| 0237 | 24 | | GK | | 4-0 | 21-51-15 | TB0147Y | C007 | BJ | | | D40972J | 9 | | | ALL | |
| 0238 | 24 | | GK | | 4-0 | 21-51-15 | TB0147Y | C003 | BJ | | | D40974J | 51 | | | ALL | |
| 0239 | 24 | | GK | | 4-0 | 21-51-15 | TB0147Y | C008 | BJ | | | D40974J | 52 | | | ALL | |
| 0240 | 24 | | GK | | 2-0 | 36-11-11 | D40972J | 18 | | | | TB0147Z | 15 | BJ | | 001-099 | |
| 0241 | 24 | | GK | | 4-0 | 26-16-11 | D41380J | 8 | | | | D42000J | 22 | | | ALL | |
| 0242 | 24 | | GK | | 4-0 | 26-18-21 | D40970J | 6 | | | | TB0147Y | A013 | BJ | | 001-099 | |
| 0242 | 24 | | GK | | 3-0 | 26-18-21 | D40970J | 6 | | | | TB0147Y | A013 | BJ | | 115-199 | |
| 0246 | 24 | | GK | | 3-0 | 77-12-41 | D02996 | 64 | | | | GD00207 | DC.. | 2 | | 001-099 | |
| 0246 | 22 | | GA | | 3-0 | 77-12-41 | D02996 | 64 | | | | GD00207 | DC.. | 2 | | 115-199 | |
| 0247 | 24 | | GK | | 2-0 | 36-11-11 | D40972J | 19 | | | | TB0147Z | 15 | BJ | | 001-099 | |
| 0248 | 24 | | GK | | 2-0 | 77-12-41 | D02996 | 58 | | | | D02996 | 53 | | | ALL | |
| 0249 | 24 | | GK | | 2-0 | 77-12-41 | D02996 | 20 | | | | D02996 | 66 | | | ALL | |
| 0250 | 24 | | GK | | 3-0 | 77-12-42 | GD00208 | DC.. | 2 | | | D02838 | 64 | | | 001-099 | |
| 0250 | 22 | | GA | | 3-0 | 77-12-42 | GD00208 | DC.. | 2 | | | D02838 | 64 | | | 115-199 | |
| 0251 | 24 | | GK | | 4-0 | 26-18-21 | D42002J | 3 | | | | TB0147Y | A013 | BJ | | 001-099 | |
| 0251 | 24 | | GK | | 3-0 | 26-18-21 | D42002J | 3 | | | | TB0147Y | A013 | BJ | | 115-199 | |
| 0252 | 24 | | GK | | 3-0 | 26-17-11 | D02824 | 39 | | | | D41990J | 14 | | | ALL | |
| 0253 | 24 | | GK | | 3-0 | 26-17-11 | SM00008 | | | WI | | D42000J | 4 | | | ALL | |
| 0254 | 24 | | GK | | 4-0 | 26-17-11 | D02824 | 27 | | | | D42000J | 5 | | | 001-099 | |
| 0254 | 24 | | GK | | 3-0 | 26-17-11 | D02824 | 27 | | | | D42000J | 5 | | | 115-199 | |
| 0255 | 24 | | GK | | 4-0 | 26-17-11 | D02824 | 5 | | | | D42000J | 3 | | | 001-099 | |
| 0255 | 24 | | GK | | 3-0 | 26-17-11 | D02824 | 5 | | | | D42000J | 3 | | | 115-199 | |
| 0256 | 22 | | GA | | 2-0 | 26-17-11 | D02824 | 35 | | | | GD00207 | AC.. | 2 | | ALL | |
| 0257 | 24 | | GK | | 2-0 | 77-12-42 | D02838 | 54 | | | | D02838 | 66 | | | ALL | |
| 0258 | 24 | | GK | | 2-0 | 77-12-42 | D02838 | 58 | | | | D02838 | 22 | | | ALL | |
| 0260 | 24 | | GK | | 4-0 | 26-17-11 | D41380J | 14 | | | | D02824 | 9 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 5

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1140 | | 286N1140 | | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | |
| 0260 | 24 | GK | | | 3-0 | 26-17-11 | D41380J | 14 | | | D02824 | 9 | | | 115-199 |
| 0261 | 24 | GK | | | 3-0 | 26-17-11 | D41990J | 13 | | | D02824 | 30 | | | ALL |
| 0262 | 24 | GK | | | 3-0 | 26-17-11 | D02824 | 40 | | | SM00008 | | WI | | ALL |
| 0263 | 24 | GK | | | 3-0 | 31-51-21 | SM00008 | | WI | | D41489J | 3 | | | ALL |
| 0280 | 22 | GA | | | 2-0 | 26-18-11 | D02824 | 36 | | | GD00207 | AC.. | 2 | | ALL |
| 0281 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 2 | | | D40812J | 10 | | | ALL |
| 0282 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 43 | | | D42000J | 6 | | | ALL |
| 0283 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 3 | | | D40810J | 4 | | | ALL |
| 0284 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 20 | | | D42000J | 1 | | | ALL |
| 0285 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 51 | | | D42000J | 2 | | | ALL |
| 0286 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 53 | | | D42004J | 1 | | | ALL |
| 0287 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 18 | | | D42004J | 2 | | | ALL |
| 0288 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 49 | | | D42000J | 7 | | | ALL |
| 0289 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 17 | | | D42000J | 8 | | | ALL |
| 0290 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 45 | | | D42000J | 9 | | | ALL |
| 0291 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 13 | | | D42000J | 10 | | | ALL |
| 0292 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 24 | | | D41990J | 3 | | | ALL |
| 0293 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 57 | | | D41990J | 4 | | | ALL |
| 0294 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 46 | | | D41990J | 5 | | | ALL |
| 0295 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 10 | | | D41990J | 6 | | | ALL |
| 0296 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 42 | | | D41990J | 44 | | | ALL |
| 0297 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 8 | | | D41990J | 45 | | | ALL |
| 0298 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 26 | | | D41990J | 46 | | | ALL |
| 0299 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 59 | | | D41990J | 47 | | | ALL |
| 0300 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 25 | | | D41990J | 48 | | | ALL |
| 0301 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 58 | | | D41990J | 49 | | | ALL |
| 0302 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 60 | | | D41990J | 50 | | | ALL |
| 0303 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 28 | | | D41990J | 51 | | | ALL |
| 0304 | 22 | GA | | | 4-0 | 26-18-11 | GD00207 | DC.. | 2 | | D04258 | 15 | | | ALL |
| 0305 | 24 | GK | | | 3-0 | 26-18-21 | TB0147Y | A013 | BJ | | D02824 | 7 | | | ALL |
| 0307 | 24 | GK | | | 3-0 | 26-18-21 | D02824 | 15 | | | D42002J | 1 | | | ALL |
| 0308 | 24 | GK | | | 3-0 | 26-18-21 | D02824 | 12 | | | D42002J | 2 | | | ALL |
| 0309 | 24 | GK | | | 3-0 | 26-18-21 | D02824 | 11 | | | D41990J | 1 | | | ALL |
| 0310 | 24 | GK | | | 3-0 | 26-18-21 | D02824 | 48 | | | D41990J | 2 | | | ALL |
| 0311 | 24 | GK | | | 3-0 | 26-18-21 | D02824 | 50 | | | D42002J | 5 | | | ALL |
| 0312 | 24 | GK | | | 3-0 | 26-18-21 | D02824 | 16 | | | D42002J | 6 | | | ALL |
| 0313 | 24 | GK | | | 3-0 | 26-18-21 | D02824 | 19 | | | D42002J | 7 | | | ALL |
| 0314 | 24 | GK | | | 3-0 | 26-18-21 | D02824 | 52 | | | D42002J | 8 | | | ALL |
| 0315 | 22 | GA | | | 3-0 | 77-12-42 | D02838 | 13 | | | TB0147Y | C010 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 6

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1140 | 286N1140 | | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | | | |
| 0315 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | SM00007 | | 9 | | 115-199 |
| 0316 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | TB0147Y | C010 | BJ | | 001-099 |
| 0316 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | SM00007 | | 9 | | 115-199 |
| 0318 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | D41990J | | 10 | | ALL |
| 0319 | 24 | | GK | | 3-0 | 77-12-42 | | D02838 | | | | D41990J | | 11 | | 001-099 |
| 0319 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | D41990J | | 11 | | 115-199 |
| 0320 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | GD00208 | DC.. | 2 | | ALL |
| 0321 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | TB0147Y | A010 | BJ | | 001-099 |
| 0321 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | SM00006 | | 9 | | 115-199 |
| 0322 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | TB0147Y | A010 | BJ | | 001-099 |
| 0322 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | SM00006 | | 9 | | 115-199 |
| 0324 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | D42004J | | 6 | | ALL |
| 0325 | 24 | | GK | | 3-0 | 77-12-41 | | D02996 | | | | D42004J | | 7 | | 001-099 |
| 0325 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | D42004J | | 7 | | 115-199 |
| 0326 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | GD00207 | DC.. | 2 | | ALL |
| 0327 | 22 | | GA | | 3-0 | 30-21-11 | | D02998 | | | | D41380J | | 9 | | ALL |
| 0328 | 22 | | GA | | 3-0 | 30-21-11 | | D02998 | | | | D42000J | | 14 | | ALL |
| 0329 | 22 | | GA | | 4-0 | 30-21-11 | | D03058 | | | | D42002J | | 16 | | ALL |
| 0330 | 22 | | GA | | 4-0 | 30-21-11 | | D03058 | | | | D42002J | | 17 | | ALL |
| 0334 | 22 | | GA | | 4-0 | 77-12-42 | | D42002J | | | | TB0147Y | C010 | BJ | | 001-099 |
| 0336 | 22 | | GA | | 2-0 | 77-12-41 | | D41380J | | | | TB0147Y | A010 | BJ | | 001-099 |
| 0337 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | TB0147Y | A010 | BJ | | 001-099 |
| 0337 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | SM00006 | | 9 | | 115-199 |
| 0338 | 22 | | GA | | 3-0 | 77-12-41 | | D02996 | | | | D42004J | | 9 | | ALL |
| 0339 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | TB0147Y | C010 | BJ | | 001-099 |
| 0339 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | SM00007 | | 9 | | 115-199 |
| 0340 | 22 | | GA | | 3-0 | 77-12-42 | | D02838 | | | | D41990J | | 12 | | ALL |
| 0344 | 24 | | GK | | 4-0 | 36-11-21 | | D40970J | | | | TB0147Z | | 5 | BJ | 001-099 |
| 0345 | 24 | | GK | | 4-0 | 36-11-21 | | D40970J | | | | TB0147Z | | 5 | BJ | 001-099 |
| 0346 | 22 | | GA | | 3-0 | 30-34-21 | | D02996 | | | | D41477J | | 48 | | ALL |
| 0347 | 22 | | GA | | 3-0 | 30-34-21 | | D02996 | | | | D41477J | | 49 | | 001-099 |
| 0347 | 22 | | GA | | 3-0 | 30-34-21 | | D41477J | | | | D02996 | | 61 | | 115-199 |
| 0348 | 22 | | GA | | 3-0 | 30-34-21 | | D02996 | | | | D41477J | | 51 | | 001-099 |
| 0348 | 22 | | GA | | 3-0 | 30-34-21 | | D41477J | | | | D02996 | | 29 | | 115-199 |
| 0349 | 22 | | GA | | 3-0 | 30-34-22 | | D02838 | | | | D41489J | | 12 | | 001-099 |
| 0349 | 22 | | GA | | 3-0 | 30-34-22 | | D41489J | | | | D02838 | | 62 | | 115-199 |
| 0350 | 22 | | GA | | 3-0 | 30-34-22 | | D02838 | | | | D41489J | | 18 | | 001-099 |
| 0350 | 22 | | GA | | 3-0 | 30-34-22 | | D41489J | | | | D02838 | | 61 | | 115-199 |
| 0351 | 22 | | GA | | 3-0 | 30-34-22 | | D02838 | | | | D41489J | | 20 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 7

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1140 | | 286N1140 | | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | |
| 0351 | 22 | GA | | | 3-0 | 30-34-22 | D41489J | 20 | | | D02838 | 29 | | | 115-199 |
| 0386 | 24 | GK | | | 3-0 | 26-15-11 | D02996 | 63 | | | D41380J | 5 | | | 001-099 |
| 0387 | 24 | GK | | | 3-0 | 26-15-11 | D02996 | 30 | | | D02838 | 63 | | | 001-099 |
| 0388 | 24 | GK | | | 4-0 | 26-15-11 | D02838 | 30 | | | D41380J | 6 | | | 001-099 |
| 0389 | 22 | GA | | | 4-0 | 30-11-11 | D41380J | 20 | | | D42004J | 23 | | | 001-099 |
| 0389 | 22 | 6A | | | 4-0 | 30-11-11 | D41380J | 20 | | | D42004J | 23 | | | 115-199 |
| 0403 | 22 | GA | | | 3-0 | 22-12-11 | D00909 | 38 | | | D41477J | 16 | | | ALL |
| 0404 | 22 | GA | | | 3-0 | 22-12-11 | D00909 | 39 | | | D41477J | 17 | | | ALL |
| 0407 | 22 | GA | | | 3-0 | 22-12-21 | D00823 | 38 | | | D41489J | 13 | | | ALL |
| 0408 | 22 | GA | | | 3-0 | 22-12-21 | D00823 | 39 | | | D41489J | 14 | | | ALL |
| 0411 | 22 | GA | | | 4-0 | 22-12-31 | D00821 | 38 | | | D41675J | 3 | | | ALL |
| 0412 | 22 | GA | | | 4-0 | 22-12-31 | D00821 | 39 | | | D41675J | 4 | | | ALL |
| 0413 | 24 | GK | | | 4-0 | 26-15-11 | D02838 | 30 | | | D41380J | 5 | | | 115-199 |
| 0414 | 24 | GK | | | 3-0 | 34-61-13 | D02996 | 50 | | | D41477J | 45 | | | ALL |
| 0415 | 24 | GK | | | 4-0 | 34-61-13 | D02838 | 50 | | | D41477J | 46 | | | ALL |
| 0424 | 22 | GA | | | 4-0 | 29-22-11 | D42000J | 16 | | | D42002J | 13 | | | 001-099 |
| 0424 | 22 | GA | | | 4-0 | 29-22-11 | D42000J | 16 | | | D42002J | 10 | | | 115-199 |
| 0431 | 24 | GK | | | 4-0 | 26-18-11 | D02824 | 44 | | | D40972J | 20 | | | ALL |
| 0432 | 24 | GK | | | 4-0 | 26-17-11 | D02824 | 1 | | | D41380J | 13 | | | ALL |
| 0433 | 24 | GK | | | 3-0 | 21-51-11 | TB0147A | C001 | 2 | | TB0147Y | A017 | BJ | | ALL |
| 0440 | 24 | GK | | | 2-0 | 21-51-14 | D02982 | 24 | | | D40974J | 35 | | | ALL |
| 0441 | 22 | GA | | | 3-0 | 21-51-23 | D03044 | 39 | | | TB0147Y | A007 | BJ | | ALL |
| 0442 | 22 | GA | | | 4-0 | 21-51-23 | D40810J | 1 | | | TB0147Y | A007 | BJ | | 001-099 |
| 0442 | 22 | GA | | | 4-0 | 21-51-23 | D41380J | 10 | | | TB0147Y | A007 | BJ | | 115-199 |
| 0443 | 24 | GK | | | 4-0 | 21-51-23 | D40976J | 40 | | | D03044 | 5 | | | ALL |
| 0445 | 24 | GK | | | 3-0 | 21-51-21 | D40976J | 23 | | | TB0147Y | C013 | BJ | | ALL |
| 0446 | 24 | GK | | | 3-0 | 21-51-13 | D02988 | 9 | | | D40974J | 42 | | | ALL |
| 0447 | 24 | GK | | | 3-0 | 21-51-13 | D02982 | 41 | | | GD00209 | DC.. | 2 | | ALL |
| 0466 | 24 | GK | | | 4-0 | 26-18-11 | D40812J | 12 | | | D04258 | 8 | | | ALL |
| 0472 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 14 | | | D04258 | 5 | | | ALL |
| 0473 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 33 | | | D04258 | 20 | | | ALL |
| 0474 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 31 | | | D04258 | 31 | | | ALL |
| 0475 | 22 | GA | | | 4-0 | 29-22-11 | D42000J | 18 | | | D42002J | 11 | | | 001-099 |
| 0475 | 22 | GA | | | 4-0 | 29-22-11 | D42000J | 18 | | | D42004J | 8 | | | 115-199 |
| 0476 | 22 | GA | | | 2-0 | 26-18-11 | D02824 | 4 | | | GD00207 | AC.. | 2 | | ALL |
| 0477 | 24 | GK | | | 3-0 | 26-18-11 | D02824 | 6 | | | D04258 | 2 | | | ALL |
| 0500 | 24 | GK | | | 3-0 | 21-51-11 | TB0147A | C002 | 2 | | SM00005 | | WI | | ALL |
| 0501 | 24 | GK | | | 4-0 | 21-51-13 | D40974J | 39 | | | TB0147Y | A003 | BJ | | ALL |
| 0505 | 24 | GK | | | 3-0 | 21-51-11 | D02998 | 35 | | | SM00005 | | WI | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 8

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---------------------------------------|----------|---------|---------|------|--------|-------|---------|------|--------|----|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1140 | 286N1140 | | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | | | | |
| 0510 | 22 | | GA | | 4-0 | 34-61-13 | | D02838 | | 16 | | GD00210 | DC.. | 2 | | ALL | |
| 0511 | 22 | | GA | | 3-0 | 34-61-13 | | D02996 | | 16 | | GD00210 | DC.. | 2 | | ALL | |
| 0512 | 22 | | GA | | 4-0 | 29-21-31 | | D02996 | | 33 | | D42002J | | 9 | | 001-099 | |
| 0512 | 22 | | GA | | 0-6 | 29-21-31 | | D02996 | | 33 | | SM00001 | | 9 | | 115-199 | |
| 0513 | 22 | | GA | | 4-0 | 29-21-31 | | D02996 | | 34 | | D02838 | | 33 | | 001-099 | |
| 0513 | 22 | | GA | | 0-6 | 29-21-31 | | D02996 | | 34 | | SM00002 | | 9 | | 115-199 | |
| 0514 | 22 | | GA | | 0-6 | 29-21-31 | | D02838 | | 33 | | SM00003 | | 9 | | 115-199 | |
| 0515 | 22 | | GA | | 4-0 | 29-21-31 | | D02838 | | 34 | | D42002J | | 20 | | 001-099 | |
| 0515 | 22 | | GA | | 0-6 | 29-21-31 | | D02838 | | 34 | | SM00004 | | 9 | | 115-199 | |
| 0516 | 18 | | GA | | 2-0 | 29-21-31 | | SM00001 | | 9 | 9 | D42002J | | 9 | 18 | 115-199 | |
| 0517 | 18 | | GA | | 4-0 | 29-21-31 | | SM00002 | | 9 | 9 | SM00003 | | 9 | | 115-199 | |
| 0518 | 18 | | GA | | 4-0 | 29-21-31 | | SM00004 | | 9 | 9 | D42002J | | 20 | 18 | 115-199 | |
| 0521 | 24 | | GK | | 4-0 | 21-51-21 | | D03046 | | 32 | | TB0147Y | A017 | BJ | | 001-099 | |
| 0521 | 24 | | GK | | 3-0 | 21-51-21 | | D03046 | | 32 | | TB0147Y | A017 | BJ | | 115-199 | |
| 0522 | 24 | | GK | | 4-0 | 21-51-11 | | D40974J | | 33 | | TB0147A | A001 | 2 | | ALL | |
| 0523 | 22 | | GA | | 4-0 | 27-48-21 | | D00821 | | 7 | | D41675J | | 7 | | ALL | |
| 0524 | 24 | | GK | | 3-0 | 26-15-11 | | D02996 | | 30 | | D02838 | | 63 | | 115-199 | |
| 0525 | 24 | | GK | | 3-0 | 26-15-11 | | D02996 | | 63 | | D41380J | | 6 | | 115-199 | |
| 0526 | 24 | | GK | | 3-0 | 21-51-23 | | D03044 | | 21 | | GD00208 | DC.. | 2 | | ALL | |
| 0527 | 24 | | GK | | 3-0 | 21-51-23 | | D03044 | | 41 | | GD00208 | DC.. | 2 | | ALL | |
| 0528 | 24 | | GK | | 3-0 | 21-51-21 | | D02988 | | 15 | | TB0147Y | C013 | BJ | | ALL | |
| 0529 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 9 | | D40810J | | 2 | | ALL | |
| 0530 | 22 | | GA | | 2-0 | 27-23-21 | | D04688 | | 10 | | GD00208 | DC.. | 2 | | ALL | |
| 0531 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 20 | | D41477J | | 10 | | ALL | |
| 0532 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 21 | | D41477J | | 14 | | ALL | |
| 0533 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 22 | | D41477J | | 15 | | ALL | |
| 0534 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 23 | | D41477J | | 41 | | ALL | |
| 0535 | 22 | | GA | | 3-0 | 27-23-21 | | D04688 | | 12 | | D41489J | | 4 | | ALL | |
| 0536 | 22 | | GA | | 3-0 | 27-23-21 | | D04688 | | 13 | | D41489J | | 5 | | ALL | |
| 0537 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 14 | | D41477J | | 42 | | ALL | |
| 0538 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 15 | | D41477J | | 53 | | ALL | |
| 0539 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 16 | | D41477J | | 54 | | ALL | |
| 0540 | 22 | | GA | | 4-0 | 27-23-21 | | D04688 | | 17 | | D41477J | | 55 | | ALL | |
| 0543 | 24 | | GK | | 3-0 | 73-21-12 | | D02998 | | 44 | | D42004J | | 16 | | ALL | |
| 0544 | 24 | | GK | | 3-0 | 73-21-12 | | D02998 | | 49 | | D42004J | | 11 | | ALL | |
| 0545 | 24 | | GK | | 3-0 | 73-21-12 | | D02998 | | 6 | | D42004J | | 12 | | ALL | |
| 0546 | 24 | | GK | | 3-0 | 73-21-12 | | D02998 | | 51 | | D42004J | | 13 | | ALL | |
| 0547 | 24 | | GK | | 3-0 | 73-21-12 | | D02998 | | 22 | | D42004J | | 14 | | ALL | |
| 0548 | 24 | | GK | | 3-0 | 73-21-12 | | D02998 | | 17 | | D42004J | | 15 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 9

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1140 | | 286N1140 | | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | |
| 0549 | 22 | GA | | | 3-0 | 73-21-12 | D02998 | 66 | | | GD00207 | DC.. | 2 | | ALL |
| 0550 | 22 | GA | | | 4-0 | 77-12-42 | D42002J | 4 | | | SM00007 | | 9 | | 115-199 |
| 0551 | 22 | GA | | | 5-0 | 77-12-41 | D41380J | 4 | | | SM00006 | | 9 | | 115-199 |
| 0552 | 24 | GK | | | 4-0 | 73-21-22 | D03058 | 44 | | | D41990J | 18 | | | ALL |
| 0553 | 24 | GK | | | 4-0 | 73-21-22 | D03058 | 49 | | | D41990J | 19 | | | ALL |
| 0554 | 24 | GK | | | 4-0 | 73-21-22 | D03058 | 6 | | | D41990J | 20 | | | ALL |
| 0555 | 24 | GK | | | 4-0 | 73-21-22 | D03058 | 51 | | | D41990J | 21 | | | ALL |
| 0556 | 24 | GK | | | 4-0 | 73-21-22 | D03058 | 22 | | | D41990J | 22 | | | ALL |
| 0557 | 24 | GK | | | 4-0 | 73-21-22 | D03058 | 17 | | | D41990J | 23 | | | ALL |
| 0558 | 24 | GK | | | 2-0 | 21-51-11 | TB0147A | A001 | 2 | | TB0147A | A002 | 2 | | ALL |
| 0561 | 22 | GA | | | 4-0 | 27-23-21 | D04688 | 18 | | | D40810J | 11 | | | ALL |
| 0562 | 22 | GA | | | 3-0 | 27-23-21 | D04688 | 19 | | | GD00208 | AC.. | 2 | | ALL |
| 0563 | 22 | GA | | | 4-0 | 30-11-11 | TB0147Z | 16 | BJ | | D03058 | 57 | | | ALL |
| 0564 | 22 | GA | | | 4-0 | 30-11-11 | TB0147Z | 16 | BJ | | D03058 | 25 | | | ALL |
| 0565 | 22 | GA | | | 3-0 | 30-11-11 | TB0147Z | 16 | BJ | | D02998 | 57 | | | ALL |
| 0566 | 22 | GA | | | 3-0 | 30-11-11 | TB0147Z | 16 | BJ | | D02998 | 25 | | | ALL |
| 0567 | 22 | GA | | | 4-0 | 30-11-11 | D41380J | 21 | | | TB0147Z | 16 | BJ | | ALL |
| 2005B | 22 | GB | AE | | 3-0 | 22-24-11 | D00909 | 41 | | | D41477J | 3 | | | ALL |
| 2005R | 22 | GB | AE | | 0-0 | 22-24-11 | D00909 | 40 | | | D41477J | 2 | | | ALL |
| 2008B | 22 | GB | AH | | 3-0 | 22-24-21 | D00823 | 41 | | | D41489J | 8 | | | ALL |
| 2008R | 22 | GB | AH | | 0-0 | 22-24-21 | D00823 | 40 | | | D41489J | 7 | | | ALL |
| 2010B | 24 | GL | AO | | 3-0 | 27-48-21 | D00823 | 35 | | | D41837J | 5 | | | ALL |
| 2010R | 24 | GL | AO | | 0-0 | 27-48-21 | D00823 | 31 | | | D41837J | 4 | | | ALL |
| 2011B | 24 | GL | AQ | | 3-0 | 27-48-21 | D00821 | 35 | | | D41839J | 5 | | | ALL |
| 2011R | 24 | GL | AQ | | 0-0 | 27-48-21 | D00821 | 31 | | | D41839J | 4 | | | ALL |
| 2012B | 24 | GL | AX | | 3-0 | 27-48-21 | D00909 | 35 | | | D41835J | 5 | | | ALL |
| 2012R | 24 | GL | AX | | 0-0 | 27-48-21 | D00909 | 31 | | | D41835J | 4 | | | ALL |
| 2501B | 24 | GF | BA | | 3-0 | 28-21-21 | D40970J | 8 | | | D02514 | 5 | | | ALL |
| 2501R | 24 | GF | BA | | 0-0 | 28-21-21 | D40970J | 7 | | | D02514 | 15 | | | ALL |
| 2501Z | | | BA | | 0-0 | 28-21-21 | D40970J | 9 | | | GD00207 | ST.. | 2 | | ALL |
| 2502B | 24 | GF | BB | | 3-0 | 28-21-21 | D40970J | 24 | | | D02514 | 17 | | | ALL |
| 2502R | 24 | GF | BB | | 0-0 | 28-21-21 | D40970J | 23 | | | D02514 | 16 | | | ALL |
| 2502Z | | | BB | | 0-0 | 28-21-21 | D40970J | 25 | | | GD00207 | ST.. | 2 | | ALL |
| 2503B | 24 | GF | BC | | 4-0 | 77-12-31 | D42002J | 14 | | | D02838 | 2 | | | ALL |
| 2503R | 24 | GF | BC | | 0-0 | 77-12-31 | D42002J | 10 | | | D02838 | 1 | | | 001-099 |
| 2503R | 24 | GF | BC | | 0-0 | 77-12-31 | D42002J | 13 | | | D02838 | 1 | | | 115-199 |
| 2503Z | | | BC | | 0-0 | 77-12-31 | D42002J | 15 | | | D02838 | DED | | | ALL |
| 2504B | 24 | GF | BD | | 3-0 | 77-12-31 | D42000J | 12 | | | D02996 | 2 | | | ALL |
| 2504R | 24 | GF | BD | | 0-0 | 77-12-31 | D42000J | 11 | | | D02996 | 1 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 10

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|---------------------------------------|-------|----------|---------|--------|-------|---------|-------------|------|--------|---------|
| | GA | CO | TY | | Equip | Term | Type | Splice | Equip | Term | | Type | Splice | |
| W1140 | 286N1140 | | | P50 ELECTRICAL CARD FILE. (continued) | | | | | | | | | | |
| 2504Z | | | | BD | 0-0 | 77-12-31 | D42000J | | 13 | D02996 | | DED | | ALL |
| 3004B | 24 | GM | AN | | 3-0 | 27-48-21 | D00823 | | 33 | D41837J | | 2 | | ALL |
| 3004R | 24 | GM | AN | | 0-0 | 27-48-21 | D00823 | | 32 | D41837J | | 1 | | ALL |
| 3004Y | 24 | GM | AN | | 0-0 | 27-48-21 | D00823 | | 34 | D41837J | | 3 | | ALL |
| 3005B | 24 | GM | AP | | 3-0 | 27-48-21 | D00821 | | 33 | D41839J | | 2 | | ALL |
| 3005R | 24 | GM | AP | | 0-0 | 27-48-21 | D00821 | | 32 | D41839J | | 1 | | ALL |
| 3005Y | 24 | GM | AP | | 0-0 | 27-48-21 | D00821 | | 34 | D41839J | | 3 | | ALL |
| 3006B | 24 | GM | AR | | 3-0 | 27-48-21 | D00909 | | 33 | D41835J | | 2 | | ALL |
| 3006R | 24 | GM | AR | | 0-0 | 27-48-21 | D00909 | | 32 | D41835J | | 1 | | ALL |
| 3006Y | 24 | GM | AR | | 0-0 | 27-48-21 | D00909 | | 34 | D41835J | | 3 | | ALL |
| PA01 | | | | | 0-0 | 27-48-21 | D00821 | | 47 | D00821 | | 66 | | ALL |
| PB01 | | | | | 0-0 | 27-48-21 | D00823 | | 47 | D00823 | | 66 | | ALL |
| PC01 | | | | | 0-0 | 27-48-21 | D00909 | | 47 | D00909 | | 66 | | ALL |
| PD01 | | | | | 0-0 | 28-21-21 | D02514 | | 7 | D02514 | | 37 | | ALL |
| PE01 | | | | | 0-0 | 77-12-42 | D02838 | | 32 | D02838 | | 45 | | 001-099 |
| PE01 | | | | | 0-0 | 78-34-21 | D02838 | | 32 | D02838 | | 45 | | 115-199 |
| PF01 | | | | | 0-0 | 21-51-13 | D02982 | | 22 | D02982 | | 38 | | ALL |
| PF02 | | | | | 0-0 | 21-51-13 | D02982 | | 27 | D02982 | | 40 | | ALL |
| PG01 | | | | | 0-0 | 21-51-11 | D02988 | | 25 | D02988 | | 35 | | ALL |
| PH01 | | | | | 0-0 | 77-12-41 | D02996 | | 32 | D02996 | | 45 | | 001-099 |
| PH01 | | | | | 0-0 | 78-34-21 | D02996 | | 32 | D02996 | | 45 | | 115-199 |
| PK01 | | | | | 0-0 | 21-51-23 | D03044 | | 22 | D03044 | | 38 | | ALL |
| PK02 | | | | | 0-0 | 21-51-23 | D03044 | | 27 | D03044 | | 40 | | ALL |
| PL01 | | | | | 0-0 | 21-51-21 | D03046 | | 25 | D03046 | | 35 | | ALL |
| PM01 | | | | | 0-0 | 21-51-21 | D03058 | | 9 | D03058 | | 65 | | ALL |
| PN01 | | | | | 0-0 | 26-18-21 | D02824 | | 29 | D02824 | | 41 | | ALL |
| PP01 | | | | | 0-0 | 73-21-12 | D02998 | | 9 | D02998 | | 65 | | ALL |
| PQ01 | | | | | 0-0 | 26-18-11 | D04258 | | 4 | D04258 | | 60 | | ALL |
| PU01 | | | | | 0-0 | 27-23-31 | D04688 | | 6 | D04688 | | 33 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1140

Page 11 End

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1161 | 286N1161 | | | E4-4 INTEGRATION | | | | | | | | | | | |
| 0002 | 20 | | GA | | 2-0 | 23-34-15 | D00739 | | 16 | | GD01765 | DC.. | 2 | | 001-099 |
| 0002 | 20 | | GA | | 2-0 | 23-34-16 | D00739 | | 16 | | GD01765 | DC.. | 2 | | 115-199 |
| 0003 | 22 | | GA | | 4-0 | 23-34-15 | D00739 | | 1 | | D41455P | | 4 | | ALL |
| 0005 | 20 | | GA | | 2-0 | 23-34-16 | D00739 | | 17 | | GD01765 | ST.. | 2 | | 115-199 |
| 0008 | 24 | | GK | | 2-0 | 23-34-16 | D41455P | | 3 | | D41702P | | 3 | | 115-199 |
| 0015 | 22 | | GA | | 4-0 | 23-34-15 | D01353 | | 55 | | D41702P | | 1 | | ALL |
| 0016 | 20 | | GA | | 3-0 | 23-34-12 | D01353 | | 16 | | SM00001 | | WI | | 001-099 |
| 0017 | 20 | | GA | | 3-0 | 23-34-12 | D01353 | | 17 | | SM00002 | | WI | | 001-099 |
| 0018 | 20 | | GA | | 3-0 | 23-34-12 | D01353 | | 18 | | SM00003 | | WI | | 001-099 |
| 0019 | 20 | | GA | | 3-0 | 23-34-12 | D01353 | | 19 | | SM00004 | | WI | | 001-099 |
| 001CO | | | | CN CN | 0-0 | 23-12-31 | D00847C | = C1 | | | D41719P | = C1 | | | 001-099 |
| 001CX | | 66 | | | 2-7 | 23-12-31 | D00847C | 1 | JD | | D41719P | = A1 | | | 001-099 |
| 0020 | 20 | | GA | | 3-0 | 23-34-12 | D01353 | | 8 | | SM00005 | | WI | | 001-099 |
| 0021 | 20 | | GA | | 3-0 | 23-34-12 | D01353 | | 9 | | SM00006 | | WI | | 001-099 |
| 0022 | 20 | | GA | | 3-0 | 23-34-12 | D01353 | | 30 | | SM00007 | | WI | | 001-099 |
| 0023 | 20 | | GA | | 3-0 | 23-34-12 | D01353 | | 32 | | SM00008 | | WI | | 001-099 |
| 0029 | 24 | | GK | | 4-0 | 23-12-31 | D00847B | C13 | | | D41529P | | 8 | | 001-099 |
| 0030 | 24 | | GK | | 4-0 | 23-12-31 | D00847B | D13 | | | D41529P | | 9 | | 001-099 |
| 0031 | 24 | | GK | | 3-0 | 23-12-31 | D00847B | B14 | | | D41455P | | 28 | | 001-099 |
| 0032 | 20 | | GA | | 3-0 | 23-12-31 | D00847B | | | AQ | GD01765 | ST.. | 2 | | 001-099 |
| 0033 | 24 | | GK | | 4-0 | 31-31-61 | D00847B | D01 | | | D41455P | | 17 | | 001-099 |
| 0034 | 16 | | GA | | 2-0 | 23-12-31 | D40688P | 10 | | | SM00014 | | WI | | 001-099 |
| 0035 | 16 | | GA | | 3-0 | 23-12-31 | D00847C | 2 | | | SM00014 | | WI | | 001-099 |
| 0036 | 16 | | GA | | 3-0 | 23-12-31 | D00847C | 4 | | | GD01765 | DC.. | 2 | | 001-099 |
| 0037 | 18 | | GA | | 2-0 | 23-12-31 | D41529P | 7 | | | SM00014 | | WI | | 001-099 |
| 0038 | 22 | | GA | | 3-0 | 23-12-31 | D00847B | D03 | | | GD01765 | DC.. | 2 | | 001-099 |
| 0039 | 24 | | GK | | 4-0 | 23-12-31 | D00847B | A03 | | | D41529P | | 5 | | 001-099 |
| 0040 | 24 | | GK | | 4-0 | 23-12-31 | D00847B | B03 | | | D41529P | | 6 | | 001-099 |
| 0041 | 24 | | GK | | 4-0 | 23-12-31 | D00847B | C03 | | | D41529P | | 1 | | 001-099 |
| 0042 | 24 | | GK | | 4-0 | 23-51-11 | D00847B | C01 | | | D41455P | | 29 | | 001-099 |
| 0043 | 20 | | GA | | 2-0 | 23-34-15 | D01353 | 12 | | | GD01765 | DC.. | 2 | | ALL |
| 0044 | 22 | | GA | | 4-0 | 23-34-15 | D01353 | 1 | | | D41455P | | 23 | | ALL |
| 0051 | 22 | | GA | | 2-0 | 23-34-15 | D41455P | 14 | | | SM00030 | | WI | | 001-099 |
| 0051 | 22 | | GA | | 3-0 | 23-34-15 | D41455P | 14 | | | SM00030 | | WI | | 115-199 |
| 0052 | 24 | | GK | | 3-0 | 23-34-15 | SM00030 | | 56 | WI | D00739 | | 56 | | 001-099 |
| 0052 | 24 | | GK | | 2-0 | 23-34-15 | SM00030 | | 56 | WI | D00739 | | 56 | | 115-199 |
| 0053 | 22 | | GA | | 4-0 | 23-34-12 | D01353 | 20 | | | D41549P | | 6 | | ALL |
| 0054 | 22 | | GA | | 4-0 | 23-34-12 | D01353 | 31 | | | D41549P | | 12 | | ALL |
| 0055 | 22 | | GA | | 4-0 | 23-34-12 | D01353 | 21 | | | D41547P | | 6 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1161 | 286N1161 | | | | E4-4 INTEGRATION (continued) | | | | | | | | | | |
| 0056 | 22 | | GA | | 4-0 | 23-34-12 | D01353 | 34 | | | D41547P | 12 | | | ALL |
| 0057 | 22 | | GA | | 4-0 | 23-34-15 | D01353 | 11 | | | D41455P | 12 | | | ALL |
| 0058 | 24 | | GK | | 3-0 | 23-34-15 | D01353 | 25 | | | SM00030 | | WI | | 001-099 |
| 0058 | 24 | | GK | | 2-0 | 23-34-15 | D01353 | 25 | | | SM00030 | | WI | | 115-199 |
| 0059 | 20 | | GA | | 2-0 | 23-34-15 | D01353 | 33 | | | GD01765 | AC.. | 2 | | ALL |
| 0060 | 22 | | GA | | 4-0 | 23-34-15 | D00739 | 10 | | | D41455P | 10 | | | ALL |
| 0062 | 22 | | GA | | 2-0 | 23-34-15 | D41455P | 13 | | | D41702P | 2 | | | 115-199 |
| 0067 | 22 | | GA | | 2-0 | 23-34-15 | D41455P | 9 | | | D41702P | 8 | | | ALL |
| 0070 | 22 | | GA | | 1-0 | 23-34-15 | D41455P | 7 | | | D41455P | 11 | | | ALL |
| 0071 | 22 | | GA | | 4-0 | 23-34-16 | D41702P | 14 | | | D00739 | 31 | | | 115-199 |
| 0072 | 22 | | GA | | 4-0 | 23-34-16 | D41702P | 15 | | | D00739 | 33 | | | 115-199 |
| 0073 | 22 | | GA | | 4-0 | 23-34-16 | D41702P | 16 | | | D00739 | 32 | | | 115-199 |
| 2001B | 18 | | GB | AB | 2-0 | 23-34-12 | SM00002 | | WI | | D41549P | 5 | 18 | | 001-099 |
| 2001B | 20 | | GB | AB | 4-0 | 23-34-12 | D01353 | 17 | | | D41549P | 5 | | | 115-199 |
| 2001R | 18 | | GB | AB | 0-0 | 23-34-12 | SM00001 | | WI | | D41549P | 15 | 18 | | 001-099 |
| 2001R | 20 | | GB | AB | 0-0 | 23-34-12 | D01353 | 16 | | | D41549P | 4 | | | 115-199 |
| 2002B | 18 | | GB | AC | 2-0 | 23-34-12 | SM00004 | | WI | | D41549P | 13 | 18 | | 001-099 |
| 2002B | 20 | | GB | AC | 4-0 | 23-34-12 | D01353 | 19 | | | D41549P | 11 | | | 115-199 |
| 2002R | 18 | | GB | AC | 0-0 | 23-34-12 | SM00003 | | WI | | D41549P | 10 | 18 | | 001-099 |
| 2002R | 20 | | GB | AC | 0-0 | 23-34-12 | D01353 | 18 | | | D41549P | 10 | | | 115-199 |
| 2003B | 18 | | GB | AD | 2-0 | 23-34-12 | SM00006 | | WI | | D41547P | 5 | 18 | | 001-099 |
| 2003B | 20 | | GB | AD | 4-0 | 23-34-12 | D01353 | 9 | | | D41547P | 5 | | | 115-199 |
| 2003R | 18 | | GB | AD | 0-0 | 23-34-12 | SM00005 | | WI | | D41547P | 15 | 18 | | 001-099 |
| 2003R | 20 | | GB | AD | 0-0 | 23-34-12 | D01353 | 8 | | | D41547P | 4 | | | 115-199 |
| 2004B | 18 | | GB | AE | 2-0 | 23-34-12 | SM00008 | | WI | | D41547P | 13 | 18 | | 001-099 |
| 2004B | 20 | | GB | AE | 4-0 | 23-34-12 | D01353 | 32 | | | D41547P | 11 | | | 115-199 |
| 2004R | 18 | | GB | AE | 0-0 | 23-34-12 | SM00007 | | WI | | D41547P | 10 | 18 | | 001-099 |
| 2004R | 20 | | GB | AE | 0-0 | 23-34-12 | D01353 | 30 | | | D41547P | 10 | | | 115-199 |
| 2040B | 24 | | GL | BO | 4-0 | 23-34-15 | D01353 | 24 | | | GD01765 | AC.. | 2 | | ALL |
| 2040R | 24 | | GL | BO | 0-0 | 23-34-15 | D01353 | 13 | | | D41455P | 27 | | | ALL |
| 2041B | 24 | | GL | AN | 3-0 | 23-51-11 | D00847B | B01 | | | D41455P | 30 | | | 001-099 |
| 2041R | 24 | | GL | AN | 0-0 | 23-51-11 | D00847B | A01 | | | D41455P | 31 | | | 001-099 |
| 2042B | 24 | | GL | AP | 3-0 | 23-51-11 | D00847B | B15 | | | D41455P | 19 | | | 001-099 |
| 2042R | 24 | | GL | AP | 0-0 | 23-51-11 | D00847B | A15 | | | D41455P | 18 | | | 001-099 |
| 2043B | 24 | | GL | AM | 3-0 | 23-21-11 | D00847B | B13 | | | D41455P | 6 | | | 001-099 |
| 2043R | 24 | | GL | AM | 0-0 | 23-21-11 | D00847B | A13 | | | D41455P | 5 | | | 001-099 |
| 2044B | 22 | | GB | CL | 4-0 | 23-34-16 | D00739 | 42 | | | D41455P | 2 | | | 115-199 |
| 2044R | 22 | | GB | CL | 0-0 | 23-34-16 | D00739 | 41 | | | D41455P | 1 | | | 115-199 |
| 2045B | 22 | | GB | AK | 4-0 | 23-34-15 | D01353 | 39 | | | D41515P | 4 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 2

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1161 | 286N1161 | | | E4-4 INTEGRATION (continued) | | | | | | | | | | | |
| 2045R | 22 | GB | AK | | 0-0 | 23-34-15 | D01353 | 40 | | | D41515P | 3 | | | ALL |
| 2046B | 22 | GB | AL | | 4-0 | 23-34-15 | D01353 | 41 | | | D41515P | 2 | | | ALL |
| 2046R | 22 | GB | AL | | 0-0 | 23-34-15 | D01353 | 42 | | | D41515P | 1 | | | ALL |
| 2501B | 22 | GU | BP | | 3-0 | 23-34-15 | D01353 | 45 | | | D00739 | 27 | | | ALL |
| 2501R | 22 | GU | BP | | 0-0 | 23-34-15 | D01353 | 46 | | | D00739 | 26 | | | ALL |
| 2501Z | | | BP | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2502B | 22 | GU | BQ | | 3-0 | 23-34-15 | D01353 | 49 | | | D00739 | 29 | | | ALL |
| 2502R | 22 | GU | BQ | | 0-0 | 23-34-15 | D01353 | 50 | | | D00739 | 28 | | | ALL |
| 2502Z | | | BQ | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2503B | 22 | GU | BR | | 3-0 | 23-34-15 | D01353 | 51 | | | D00739 | 48 | | | ALL |
| 2503R | 22 | GU | BR | | 0-0 | 23-34-15 | D01353 | 52 | | | D00739 | 47 | | | ALL |
| 2503Z | | | BR | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2504B | 22 | GU | BS | | 3-0 | 23-34-15 | D01353 | 53 | | | D00739 | 52 | | | ALL |
| 2504R | 22 | GU | BS | | 0-0 | 23-34-15 | D01353 | 54 | | | D00739 | 51 | | | ALL |
| 2504Z | | | BS | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2505B | 22 | GU | BT | | 3-0 | 23-34-15 | D01353 | 56 | | | D00739 | 50 | | | ALL |
| 2505R | 22 | GU | BT | | 0-0 | 23-34-15 | D01353 | 57 | | | D00739 | 49 | | | ALL |
| 2505Z | | | BT | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2506B | 22 | GU | BU | | 3-0 | 23-34-15 | D01353 | 58 | | | D00739 | 54 | | | ALL |
| 2506R | 22 | GU | BU | | 0-0 | 23-34-15 | D01353 | 59 | | | D00739 | 53 | | | ALL |
| 2506Z | | | BU | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2507B | 22 | GU | BV | | 3-0 | 23-34-15 | D01353 | 60 | | | D00739 | 61 | | | ALL |
| 2507R | 22 | GU | BV | | 0-0 | 23-34-15 | D01353 | 61 | | | D00739 | 60 | | | ALL |
| 2507Z | | | BV | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2508B | 22 | GU | BW | | 3-0 | 23-34-15 | D01353 | 62 | | | D00739 | 65 | | | ALL |
| 2508R | 22 | GU | BW | | 0-0 | 23-34-15 | D01353 | 63 | | | D00739 | 64 | | | ALL |
| 2508Z | | | BW | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2509B | 22 | GU | BX | | 3-0 | 23-34-15 | D01353 | 64 | | | D00739 | 63 | | | ALL |
| 2509R | 22 | GU | BX | | 0-0 | 23-34-15 | D01353 | 65 | | | D00739 | 62 | | | ALL |
| 2509Z | | | BX | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2510B | 22 | GU | BY | | 3-0 | 23-34-15 | D01353 | 66 | | | D00739 | 67 | | | ALL |
| 2510R | 22 | GU | BY | | 0-0 | 23-34-15 | D01353 | 67 | | | D00739 | 66 | | | ALL |
| 2510Z | | | BY | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2511B | 22 | GU | CG | | 3-0 | 23-34-15 | D01353 | 47 | | | D00739 | 25 | | | ALL |
| 2511R | 22 | GU | CG | | 0-0 | 23-34-15 | D01353 | 48 | | | D00739 | 24 | | | ALL |
| 2511Z | | | CG | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |
| 2512B | 22 | GU | CM | | 3-0 | 23-34-15 | D01353 | 43 | | | D00739 | 23 | | | ALL |
| 2512R | 22 | GU | CM | | 0-0 | 23-34-15 | D01353 | 44 | | | D00739 | 22 | | | ALL |
| 2512Z | | | CM | | 0-0 | 23-34-15 | D01353 | DED | | | D00739 | DED | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 3

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1161 | 286N1161 | | | E4-4 INTEGRATION (continued) | | | | | | | | | | | |
| 3001B | 24 | GM | AA | | 4-0 | 23-34-16 | D00739 | | 15 | | D41702P | 6 | | | 115-199 |
| 3001R | 24 | GM | AA | | 0-0 | 23-34-16 | D00739 | | 14 | | D41702P | 5 | | | 115-199 |
| 3001Y | 24 | GM | AA | | 0-0 | 23-34-16 | D00739 | | 18 | | D41702P | 7 | | | 115-199 |
| 5001B | 24 | W9 | AF | | 4-0 | 23-34-12 | D01353 | | 27 | | D41549P | 2 | | | ALL |
| 5001W | 24 | W9 | AF | | 0-0 | 23-34-12 | D01353 | | 14 | | D41549P | 3 | | | ALL |
| 5001Z | | | AF | | 0-0 | 23-34-12 | D01353 | | 6 | | D41549P | 1 | | | ALL |
| 5002B | 24 | W9 | AG | | 4-0 | 23-34-12 | D01353 | | 22 | | D41549P | 8 | | | ALL |
| 5002W | 24 | W9 | AG | | 0-0 | 23-34-12 | D01353 | | 23 | | D41549P | 9 | | | ALL |
| 5002Z | | | AG | | 0-0 | 23-34-12 | D01353 | | 35 | | D41549P | 7 | | | ALL |
| 5003B | 24 | W9 | AH | | 4-0 | 23-34-12 | D01353 | | 28 | | D41547P | 2 | | | ALL |
| 5003W | 24 | W9 | AH | | 0-0 | 23-34-12 | D01353 | | 15 | | D41547P | 3 | | | ALL |
| 5003Z | | | AH | | 0-0 | 23-34-12 | D01353 | | 7 | | D41547P | 1 | | | ALL |
| 5004B | 24 | W9 | AJ | | 4-0 | 23-34-12 | D01353 | | 36 | | D41547P | 8 | | | ALL |
| 5004W | 24 | W9 | AJ | | 0-0 | 23-34-12 | D01353 | | 38 | | D41547P | 9 | | | ALL |
| 5004Z | | | AJ | | 0-0 | 23-34-12 | D01353 | | 37 | | D41547P | 7 | | | ALL |
| 5005B | 24 | G2 | AR | | 4-0 | 23-12-31 | D00847B | B07 | | | D41529P | 12 | | | 001-099 |
| 5005R | 24 | G2 | AR | | 0-0 | 23-12-31 | D00847B | A07 | | | D41529P | 11 | | | 001-099 |
| 5005Z | | | AR | | 0-0 | 23-12-31 | D00847B | | | AQ | D41529P | 3 | | | 001-099 |
| W1163 | 286N1163 | | | E4-3 SHELF | | | | | | | | | | | |
| 0001 | 22 | GA | | | 2-3 | 23-21-11 | D00135C | | 2 | | D40686J | 1 | | | 001-099 |
| 0001 | 22 | GA | | | 2-0 | 23-21-11 | D00135C | | 2 | | D40686J | 1 | | | 115-199 |
| 0002 | 22 | GA | | | 3-10 | 23-21-11 | D00135C | | 3 | | GD01750 | DC.. | 2 | | 001-099 |
| 0002 | 22 | GA | | | 4-0 | 23-21-11 | D00135C | | 3 | | GD01750 | DC.. | 2 | | 115-199 |
| 0003 | 22 | GA | | | 3-10 | 23-21-11 | D00135C | | 4 | | GD01750 | ST.. | 2 | | 001-099 |
| 0003 | 22 | GA | | | 4-0 | 23-21-11 | D00135C | | 4 | | GD01750 | ST.. | 2 | | 115-199 |
| 0004 | 22 | GA | | | 4-0 | 23-21-11 | D00135B | A04 | | | GD01750 | DC.. | 2 | | ALL |
| 0005 | 24 | GK | | | 4-5 | 23-12-11 | D00125B | B14 | | | D41319J | 2 | | | 001-099 |
| 0005 | 24 | GK | | | 4-0 | 23-12-11 | D00125B | B14 | | | D41319J | 2 | | | 115-199 |
| 0006 | 24 | GK | | | 3-7 | 23-12-21 | D00129B | B14 | | | D41371J | 9 | | | 001-099 |
| 0006 | 24 | GK | | | 4-0 | 23-12-21 | D00129B | B14 | | | D41371J | 9 | | | 115-199 |
| 0007 | 24 | GK | | | 3-11 | 23-21-11 | D00135B | D06 | | | D41541J | 1 | | | 001-099 |
| 0007 | 24 | GK | | | 4-0 | 23-21-11 | D00135B | D06 | | | D41541J | 1 | | | 115-199 |
| 0008 | 24 | GK | | | 3-11 | 23-21-11 | D00135B | A07 | | | D41541J | 2 | | | 001-099 |
| 0008 | 24 | GK | | | 4-0 | 23-21-11 | D00135B | A07 | | | D41541J | 2 | | | 115-199 |
| 0009 | 24 | GK | | | 3-11 | 23-21-11 | D00135B | B07 | | | D41541J | 3 | | | 001-099 |
| 0009 | 24 | GK | | | 4-0 | 23-21-11 | D00135B | B07 | | | D41541J | 3 | | | 115-199 |
| 0010 | 24 | GK | | | 3-11 | 23-21-11 | D00135B | C07 | | | D41541J | 4 | | | 001-099 |
| 0010 | 24 | GK | | | 4-0 | 23-21-11 | D00135B | C07 | | | D41541J | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 4

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-----|------------------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1163 | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | | |
| 0011 | 24 | | GK | | 3-11 | 23-21-11 | D00135B | D07 | | | D41541J | 5 | | | 001-099 |
| 0011 | 24 | | GK | | 4-0 | 23-21-11 | D00135B | D07 | | | D41541J | 5 | | | 115-199 |
| 0012 | 24 | | GK | | 3-11 | 23-21-11 | D00135B | A01 | | | D41541J | 6 | | | 001-099 |
| 0012 | 24 | | GK | | 4-0 | 23-21-11 | D00135B | A01 | | | D41541J | 6 | | | 115-199 |
| 0013 | 24 | | GK | | 3-11 | 23-21-11 | D00135B | B01 | | | D41541J | 7 | | | 001-099 |
| 0013 | 24 | | GK | | 4-0 | 23-21-11 | D00135B | B01 | | | D41541J | 7 | | | 115-199 |
| 0014 | 24 | | GK | | 3-11 | 23-21-11 | D00135B | C01 | | | D41541J | 8 | | | 001-099 |
| 0014 | 24 | | GK | | 4-0 | 23-21-11 | D00135B | C01 | | | D41541J | 8 | | | 115-199 |
| 0015 | 24 | | GK | | 3-11 | 23-21-11 | D00135B | D01 | | | D41541J | 9 | | | 001-099 |
| 0015 | 24 | | GK | | 4-0 | 23-21-11 | D00135B | D01 | | | D41541J | 9 | | | 115-199 |
| 0016 | 24 | | GK | | 3-11 | 23-21-11 | D00135B | A02 | | | D41541J | 10 | | | 001-099 |
| 0016 | 24 | | GK | | 4-0 | 23-21-11 | D00135B | A02 | | | D41541J | 10 | | | 115-199 |
| 0017 | 24 | | GK | | 3-11 | 23-21-11 | D00135B | D03 | | | D41541J | 16 | | | 001-099 |
| 0017 | 24 | | GK | | 4-0 | 23-21-11 | D00135B | D03 | | | D41541J | 16 | | | 115-199 |
| 0018 | 24 | | GK | | 2-2 | 23-21-11 | D41541J | 11 | | | TB0141Z | 1 | BJ | | 001-099 |
| 0018 | 24 | | GK | | 4-0 | 23-21-11 | D41541J | 11 | | | TB0141Z | 1 | BJ | | 115-199 |
| 0019 | 24 | | GK | | 2-2 | 23-21-11 | D41541J | 12 | | | TB0141Z | 2 | BJ | | 001-099 |
| 0019 | 24 | | GK | | 4-0 | 23-21-11 | D41541J | 12 | | | TB0141Z | 2 | BJ | | 115-199 |
| 001CO | | | | CC | 0-0 | 23-12-11 | D00125C | = C1 | | | D41721J | = C1 | | | 001-099 |
| 001CO | | | | CC | 0-0 | 23-12-21 | D00129C | = C1 | | | D41731J | = C1 | | | 115-199 |
| 001CX | | 66 | | CC | 1-1 | 23-12-11 | D00125C | 1 | JD | | D41721J | = A1 | | | 001-099 |
| 001CX | | 66 | | CC | 3-0 | 23-12-21 | D00129C | 1 | JD | | D41731J | = A1 | | | 115-199 |
| 0020 | 24 | | GK | | 2-2 | 23-21-11 | D41541J | 14 | | | TB0141Z | 3 | BJ | | 001-099 |
| 0020 | 24 | | GK | | 4-0 | 23-21-11 | D41541J | 14 | | | TB0141Z | 3 | BJ | | 115-199 |
| 0021 | 24 | | GK | | 2-2 | 23-21-11 | D41541J | 15 | | | TB0141Z | 4 | BJ | | 001-099 |
| 0021 | 24 | | GK | | 4-0 | 23-21-11 | D41541J | 15 | | | TB0141Z | 4 | BJ | | 115-199 |
| 0022 | 22 | | GA | | 4-0 | 23-21-11 | D00135B | A08 | | | GD01750 | DC.. | 2 | | ALL |
| 0023 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B09 | | | D00849 | 1 | | | 001-099 |
| 0023 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | B09 | | | D00849 | 1 | | | 115-199 |
| 0024 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | A10 | | | D00849 | 2 | | | 001-003, 005 |
| 0024 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | A10 | | | D00849 | 2 | VP | | 004, 006-099 |
| 0024 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | A10 | | | D00849 | 2 | | | 115-199 |
| 0025 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B10 | | | D00849 | 3 | VP | | 001-004, 006-009 |
| 0025 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B10 | | | D00849 | 3 | | | 005, 010-099 |
| 0025 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | B10 | | | D00849 | 3 | VP | | 115-199 |
| 0026 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C10 | | | D00849 | 4 | | | 001-004, 006-099 |
| 0026 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C10 | | | D00849 | 4 | VP | | 005 |
| 0026 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | C10 | | | D00849 | 4 | VP | | 115-199 |
| 0027 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | D10 | | | D00849 | 5 | | | 001-006, 009-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 5

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | | |
| 0027 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | D10 | | | D00849 | 5 | VP | | 007-008 |
| 0027 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | D10 | | | D00849 | 5 | | | 115-199 |
| 0028 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | A11 | | | D00849 | 6 | VP | | 001, 004, 006, 009 |
| 0028 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | A11 | | | D00849 | 6 | | | 002-003, 005, 007-008, 010-099 |
| 0028 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | A11 | | | D00849 | 6 | | | 115-199 |
| 0029 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B11 | | | D00849 | 7 | VP | | 001, 004, 006, 009-099 |
| 0029 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B11 | | | D00849 | 7 | | | 002-003, 005, 007-008 |
| 0029 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | B11 | | | D00849 | 7 | | | 115-199 |
| 002CO | | | | CB | 0-0 | 23-12-21 | D00129C | = C1 | | | D41731J | = C1 | | | 001-099 |
| 002CO | | | | CB | 0-0 | 23-12-11 | D00125C | = C1 | | | D41721J | = C1 | | | 115-199 |
| 002CX | | 66 | | CB | 3-0 | 23-12-21 | D00129C | 1 | JD | | D41731J | = A1 | | | 001-099 |
| 002CX | | 66 | | CB | 1-2 | 23-12-11 | D00125C | 1 | JD | | D41721J | = A1 | | | 115-199 |
| 0030 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C11 | | | D00849 | 8 | | | 001, 005 |
| 0030 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C11 | | | D00849 | 8 | VP | | 002-004, 006-099 |
| 0030 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | C11 | | | D00849 | 8 | VP | | 115-199 |
| 0031 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | D11 | | | D00849 | 9 | VP | | 001-099 |
| 0031 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | D11 | | | D00849 | 9 | VP | | 115-199 |
| 0032 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | A13 | | | D00849 | 10 | | | 001, 003-007, 009-099 |
| 0032 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | A13 | | | D00849 | 10 | VP | | 002, 008 |
| 0032 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | A13 | | | D00849 | 10 | VP | | 115-199 |
| 0033 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B13 | | | D00849 | 11 | | | 001-002, 004, 006-008 |
| 0033 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B13 | | | D00849 | 11 | VP | | 003, 005, 009-099 |
| 0033 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | B13 | | | D00849 | 11 | | | 115-199 |
| 0034 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C13 | | | D00849 | 12 | VP | | 001-003, 010-099 |
| 0034 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C13 | | | D00849 | 12 | | | 004-009 |
| 0034 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | C13 | | | D00849 | 12 | VP | | 115-199 |
| 0035 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | D13 | | | D00849 | 13 | | | 001-003, 010-099 |
| 0035 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | D13 | | | D00849 | 13 | VP | | 004-009 |
| 0035 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | D13 | | | D00849 | 13 | VP | | 115-199 |
| 0036 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | A15 | | | D00849 | 14 | | | 001-002, 005-010 |
| 0036 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | A15 | | | D00849 | 14 | VP | | 003-004, 011-099 |
| 0036 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | A15 | | | D00849 | 14 | | | 115-199 |
| 0037 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B15 | | | D00849 | 15 | | | 001-002, 004-005, 010-099 |
| 0037 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | B15 | | | D00849 | 15 | VP | | 003, 006-009 |
| 0037 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | B15 | | | D00849 | 15 | VP | | 115-199 |
| 0038 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C15 | | | D00849 | 16 | | | 001-002, 005, 007-008 |
| 0038 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C15 | | | D00849 | 16 | VP | | 003-004, 006, 009-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 6

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|-------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0038 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | C15 | | | D00849 | 16 | VP | | 115-199 |
| 0039 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | D15 | | | D00849 | 17 | | | 001-002, 005 |
| 0039 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | D15 | | | D00849 | 17 | VP | | 003-004, 006-099 |
| 0039 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | D15 | | | D00849 | 17 | VP | | 115-199 |
| 003CO | | | | CS | 0-0 | 23-11-11 | D00299B | = C71 | | | D42043J | = C1 | | | 001-099 |
| 003CX | | 65 | | CS | 2-6 | 23-11-11 | D00299B | 71 | 5E | | D42043J | = A1 | | | 001-099 |
| 0040 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | C09 | | | D00849 | 18 | | | 001-099 |
| 0040 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | C09 | | | D00849 | 18 | | | 115-199 |
| 0041 | 24 | | GK | | 2-11 | 23-21-12 | D00135B | D09 | | | D00849 | 19 | | | 001-099 |
| 0041 | 24 | | GK | | 3-0 | 23-21-12 | D00135B | D09 | | | D00849 | 19 | | | 115-199 |
| 0061 | 24 | | GK | | 2-7 | 23-31-11 | D00007B | A02 | | | D00005B | A09 | | | 001-099 |
| 0063 | 20 | | GA | | 3-0 | 23-51-15 | D41220J | | | AV | GD01754 | ST.. | 2 | | 115-199 |
| 0070 | 24 | | GK | | 3-0 | 23-21-11 | D41541J | 13 | | | TB0141Z | 46 | BJ | | 001-099 |
| 0072 | 22 | | GA | | 3-4 | 23-42-11 | D41541J | 42 | | | D00005B | C01 | | | 001-099 |
| 0126 | 24 | | GK | | 2-6 | 23-31-41 | D00005B | C09 | | | TB0141A | C059 | 2 | * | 001-099 |
| 0126 | 24 | | GK | | 3-0 | 23-31-41 | D00005B | C12 | | | TB0141A | C059 | 2 | * | 115-199 |
| 0127 | 20 | | GA | | 1-6 | 23-42-11 | D41551J | | | XX | GD01755 | ST.. | 2 | | 001-099 |
| 0138 | 20 | | GA | | 2-6 | 23-31-11 | D40734J | 10 | | | TB0141Z | 35 | BJ | | 001-099 |
| 0138 | 20 | | GA | | 3-0 | 23-31-11 | D40734J | 10 | | | TB0141Z | 40 | BJ | | 115-199 |
| 0139 | 20 | | GA | | 2-5 | 23-31-11 | D00007C | 2 | | | TB0141Z | 35 | BJ | | 001-099 |
| 0139 | 20 | | GA | | 3-0 | 23-31-11 | D00007C | 2 | | | TB0141Z | 40 | BJ | | 115-199 |
| 0140 | 20 | | GA | | 3-0 | 23-31-11 | D00007C | 4 | | | GD01752 | DC.. | 2 | | 001-099 |
| 0140 | 20 | | GA | | 3-0 | 23-31-11 | D00007C | 4 | | | GD01752 | ST.. | 2 | | 115-199 |
| 0141 | 20 | | GA | | 3-1 | 23-31-11 | D41453J | 43 | | | TB0141Z | 35 | BJ | | 001-099 |
| 0141 | 20 | | GA | | 4-0 | 23-31-11 | D41453J | 43 | | | TB0141Z | 40 | BJ | | 115-199 |
| 0142 | 24 | | GK | | 3-1 | 23-31-11 | D00007B | C02 | | | TB0141Z | 5 | BJ | | 001-099 |
| 0142 | 24 | | GK | | 3-0 | 23-31-11 | D00007B | C02 | | | TB0141Y | A006 | BJ | | 115-199 |
| 0143 | 22 | | GA | | 3-1 | 23-31-19 | D00007B | D04 | | | TB0141Y | C075 | BJ | | 001-099 |
| 0143 | 24 | | GK | | 3-0 | 23-31-11 | D00007B | D04 | | | TB0141Y | C006 | BJ | | 115-199 |
| 0144 | 24 | | GK | | 3-0 | 23-31-11 | D00005B | D12 | | | TB0141Y | C006 | BJ | | 115-199 |
| 0145 | 24 | | GK | | 3-4 | 23-31-11 | D00005B | D11 | | | TB0141Z | 5 | BJ | | 001-099 |
| 0145 | 24 | | GK | | 3-0 | 23-31-11 | D00005B | D11 | | | TB0141Y | A006 | BJ | | 115-199 |
| 0146 | 22 | | GA | | 2-9 | 23-31-11 | D00005B | D08 | | | TB0141Z | 35 | BJ | | 001-099 |
| 0146 | 22 | | GA | | 3-0 | 23-31-11 | D00005B | D08 | | | TB0141Z | 40 | BJ | | 115-199 |
| 0147 | 22 | | GA | | 3-4 | 23-31-11 | D00005B | D09 | | | GD01752 | DC.. | 2 | | 001-099 |
| 0147 | 22 | | GA | | 3-0 | 23-31-11 | D00005B | D09 | | | GD01752 | ST.. | 2 | | 115-199 |
| 0150 | 24 | | GK | | 2-10 | 23-31-19 | D41820J | 1 | | | D00007B | D05 | | | 001-099 |
| 0150 | 24 | | GK | | 3-0 | 23-34-16 | D41453J | 19 | | | D00007B | D05 | | | 115-199 |
| 0151 | 22 | | GA | | 2-11 | 23-31-13 | D41453J | 50 | | | D00007B | D11 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 7

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0151 | 22 | | GA | | 3-0 | 23-31-13 | D41453J | 50 | | | D00007B | D11 | | | 115-199 |
| 0152 | 22 | | GA | | 2-11 | 23-31-13 | D41453J | 51 | | | D00007B | C11 | | | 001-099 |
| 0152 | 22 | | GA | | 3-0 | 23-31-13 | D41453J | 51 | | | D00007B | C11 | | | 115-199 |
| 0153 | 24 | | GK | | 2-3 | 23-31-13 | TB0141Y | A043 | BJ | | D00007B | D09 | | | 001-099 |
| 0153 | 24 | | GK | | 3-0 | 23-31-13 | TB0141Y | A043 | BJ | | D00007B | D09 | | | 115-199 |
| 0154 | 24 | | GK | | 0-7 | 23-31-13 | D00007B | A10 | | | D00007B | B10 | | | 001-099 |
| 0154 | 24 | | GK | | 1-0 | 23-31-13 | D00007B | A10 | | | D00007B | B10 | | | 115-199 |
| 0155 | 24 | | GK | | 2-11 | 23-31-13 | D41453J | 21 | | | D00007B | C09 | | | 001-099 |
| 0155 | 24 | | GK | | 3-0 | 23-31-13 | D41453J | 21 | | | D00007B | C09 | | | 115-199 |
| 0156 | 24 | | GK | | 2-7 | 23-31-13 | D00007B | D10 | | | D00005B | C11 | | | 001-099 |
| 0156 | 24 | | GK | | 3-0 | 23-31-13 | D00007B | D10 | | | D00005B | C11 | | | 115-199 |
| 0157 | 24 | | GK | | 2-7 | 23-31-13 | D00007B | B11 | | | D00005B | C10 | | | 001-099 |
| 0158 | 24 | | GK | | 2-7 | 23-31-13 | D00007B | C13 | | | D00005B | B10 | | | 001-099 |
| 0158 | 24 | | GK | | 3-0 | 23-31-13 | D00007B | C13 | | | D00005B | B10 | | | 115-199 |
| 0159 | 24 | | GK | | 2-7 | 23-31-13 | D00007B | D13 | | | D00005B | B11 | | | 001-099 |
| 0159 | 24 | | GK | | 3-0 | 23-31-13 | D00007B | D13 | | | D00005B | B11 | | | 115-199 |
| 0160 | 24 | | GK | | 2-7 | 23-31-13 | D00007B | A09 | | | D00005B | B08 | | | 001-099 |
| 0160 | 24 | | GK | | 3-0 | 23-31-13 | D00007B | A09 | | | D00005B | B08 | | | 115-199 |
| 0161 | 24 | | GK | | 2-7 | 23-31-13 | D00007B | B09 | | | D00005B | B09 | | | 001-099 |
| 0161 | 24 | | GK | | 3-0 | 23-31-13 | D00007B | B09 | | | D00005B | B09 | | | 115-199 |
| 0162 | 22 | | GA | | 4-4 | 23-34-15 | TB0141A | A053 | 2 | | SM00015 | | WI | | 001-099 |
| 0162 | 22 | | GA | | 3-0 | 23-34-15 | SM00015 | | WI | | TB0141A | A053 | 2 | | 115-199 |
| 0163 | 22 | | GA | | 4-4 | 23-34-15 | TB0141A | A054 | 2 | | SM00015 | | WI | | 001-099 |
| 0163 | 22 | | GA | | 3-0 | 23-34-15 | SM00015 | | WI | | TB0141A | A054 | 2 | | 115-199 |
| 0164 | 24 | | GK | | 3-1 | 23-34-15 | D41453J | 26 | | | TB0141Z | 35 | BJ | | 001-099 |
| 0164 | 24 | | GK | | 3-0 | 23-34-15 | D41453J | 26 | | | TB0141Z | 40 | BJ | | 115-199 |
| 0165 | 22 | | GA | | 4-4 | 23-34-15 | TB0141A | A055 | 2 | | SM00015 | | WI | | 001-099 |
| 0165 | 22 | | GA | | 3-0 | 23-34-15 | SM00015 | | WI | | TB0141A | A055 | 2 | | 115-199 |
| 0166 | 22 | | GA | | 2-5 | 23-34-15 | TB0141Y | C075 | BJ | | TB0141A | C055 | 2 | | 001-099 |
| 0166 | 22 | | GA | | 3-0 | 23-34-15 | TB0141Y | C006 | BJ | | TB0141A | C055 | 2 | | 115-199 |
| 0168 | 24 | | GK | | 2-6 | 23-31-41 | D41453J | 13 | | | TB0141A | C059 | 2 | | 001-099 |
| 0168 | 24 | | GK | | 3-0 | 23-31-41 | D41453J | 13 | | | TB0141A | C059 | 2 | * | 115-199 |
| 0169 | 24 | | GK | | 2-6 | 23-31-41 | D41453J | 14 | | | TB0141A | C056 | 2 | | 001-099 |
| 0169 | 24 | | GK | | 4-0 | 23-31-41 | D41453J | 14 | | | TB0141A | C056 | 2 | | 115-199 |
| 0170 | 24 | | GK | | 2-6 | 23-31-41 | D41453J | 15 | | | TB0141A | C057 | 2 | | 001-099 |
| 0170 | 24 | | GK | | 4-0 | 23-31-41 | D41453J | 15 | | | TB0141A | C057 | 2 | | 115-199 |
| 0171 | 24 | | GK | | 2-6 | 23-31-41 | D41453J | 16 | | | TB0141A | C058 | 2 | | 001-099 |
| 0171 | 24 | | GK | | 4-0 | 23-31-41 | D41453J | 16 | | | TB0141A | C058 | 2 | | 115-199 |
| 0172 | 22 | | GA | | 3-6 | 23-34-15 | TB0141A | C054 | 2 | | TB0141Z | 5 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 8

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | |
| 0172 | 24 | GK | | | 3-0 | 23-34-15 | TB0141Y | A006 | BJ | | TB0141A | C054 | 2 | | 115-199 |
| 0173 | 22 | GA | | | 3-5 | 23-34-15 | TB0141A | C053 | 2 | | TB0141Z | 7 | BJ | | 001-099 |
| 0173 | 24 | GK | | | 3-0 | 23-34-15 | TB0141Z | 7 | BJ | | TB0141A | C053 | 2 | | 115-199 |
| 0174 | 22 | GA | | | 4-6 | 23-34-15 | D41453J | 24 | | | SM00015 | | WI | | 001-099 |
| 0174 | 22 | GA | | | 3-0 | 23-34-15 | D41453J | 24 | | | SM00015 | | WI | | 115-199 |
| 0175 | 24 | GK | | | 4-0 | 23-41-11 | D41371J | 20 | | | GD01753 | ST.. | 2 | | 115-199 |
| 0176 | 24 | GK | | | 3-0 | 23-41-11 | D41648J | 3 | | | GD01753 | ST.. | 2 | | 115-199 |
| 0177 | 22 | GA | | | 3-10 | 23-42-11 | D41700J | 2 | | | SM00006 | | WI | | 001-099 |
| 0178 | 22 | GA | | | 3-4 | 23-42-11 | D40734J | 12 | | | D00005A | D01 | | | 001-099 |
| 0178 | 22 | GA | | | 3-0 | 23-42-11 | D40734J | 12 | | | TB0141Y | C043 | BJ | | 115-199 |
| 0179 | 22 | GA | | | 2-11 | 23-42-11 | D00005A | D02 | | | GD01753 | DC.. | 2 | | 001-099 |
| 0179 | 22 | GA | | | 3-0 | 23-42-11 | D00005A | D02 | | | GD01753 | DC.. | 2 | | 115-199 |
| 0180 | 22 | GA | | | 3-5 | 23-42-11 | D41541J | 30 | | | D00005A | C08 | | | 001-099 |
| 0180 | 22 | GA | | | 3-0 | 23-42-11 | D41541J | 30 | | | D00005A | C08 | | | 115-199 |
| 0181 | 22 | GA | | | 3-5 | 23-42-11 | D41541J | 19 | | | D00005A | C09 | | | 001-099 |
| 0181 | 22 | GA | | | 3-0 | 23-42-11 | D41541J | 19 | | | D00005A | C09 | | | 115-199 |
| 0182 | 22 | GA | | | 3-5 | 23-42-11 | D41541J | 20 | | | D00005A | C10 | | | 001-099 |
| 0182 | 22 | GA | | | 3-0 | 23-42-11 | D41541J | 20 | | | D00005A | C10 | | | 115-199 |
| 0183 | 22 | GA | | | 3-5 | 23-42-11 | D41541J | 33 | | | D00005A | C11 | | | 001-099 |
| 0183 | 22 | GA | | | 3-0 | 23-42-11 | D41541J | 33 | | | D00005A | C11 | | | 115-199 |
| 0184 | 20 | GA | | | 1-6 | 23-42-11 | D41551J | | | AK | GD01755 | ST.. | 2 | | 115-199 |
| 0185 | 22 | GA | | | 3-5 | 23-42-11 | D41700J | 4 | | | D00005A | C12 | | | 001-099 |
| 0185 | 22 | GA | | | 3-0 | 23-42-11 | D41700J | 4 | | | D00005A | C12 | | | 115-199 |
| 0186 | 22 | GA | | | 4-3 | 23-42-11 | D00005A | C13 | | | SM00006 | | WI | | 001-099 |
| 0186 | 22 | GA | | | 3-0 | 23-42-11 | D00005A | C13 | | | TB0141Y | C044 | BJ | | 115-199 |
| 0187 | 22 | GA | | | 3-10 | 23-42-11 | D41700J | 6 | | | SM00006 | | WI | | 001-099 |
| 0187 | 22 | GA | | | 4-0 | 23-42-11 | D41700J | 1 | | | TB0141Y | C044 | BJ | | 115-199 |
| 0188 | 22 | GA | | | 3-5 | 23-42-11 | D41700J | 3 | | | D00005A | C14 | | | 001-099 |
| 0188 | 22 | GA | | | 3-0 | 23-42-11 | D41700J | 3 | | | D00005A | C14 | | | 115-199 |
| 0189 | 20 | GA | | | 1-6 | 23-42-11 | D41551J | | | AL | GD01755 | ST.. | 2 | | ALL |
| 0190 | 20 | GA | | | 1-6 | 23-42-11 | D41551J | | | AI | GD01755 | ST.. | 2 | | ALL |
| 0191 | 20 | GA | | | 1-6 | 23-42-11 | D41551J | | | AJ | GD01755 | ST.. | 2 | | ALL |
| 0192 | 22 | GA | | | 2-8 | 23-51-11 | D40672J | 9 | | | D00005B | A01 | | | 001-099 |
| 0192 | 22 | GA | | | 4-0 | 23-51-11 | D40672J | 9 | | | D00005B | A01 | | | 115-199 |
| 0193 | 22 | GA | | | 2-10 | 23-51-11 | D00005B | A02 | | | GD01753 | DC.. | 2 | | 001-099 |
| 0193 | 22 | GA | | | 3-0 | 23-51-11 | D00005B | A02 | | | GD01753 | DC.. | 2 | | 115-199 |
| 0194 | 22 | GA | | | 2-10 | 23-51-11 | D00005B | C02 | | | GD01754 | ST.. | 2 | | 001-099 |
| 0194 | 22 | GA | | | 3-0 | 23-51-11 | D00005B | C02 | | | GD01754 | ST.. | 2 | | 115-199 |
| 0195 | 24 | GK | | | 2-7 | 23-51-11 | D41648J | 6 | | | D00005B | B07 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 9

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0195 | 24 | | GK | | 4-0 | 23-51-11 | D41648J | | 6 | | D00005B | B07 | | | 115-199 |
| 0196 | 24 | | GK | | 2-7 | 23-51-11 | D41648J | | 5 | | D00005B | A06 | | | 001-099 |
| 0196 | 24 | | GK | | 3-0 | 23-51-11 | D41648J | | 5 | | D00005B | A06 | | | 115-199 |
| 0197 | 20 | | GA | | 3-1 | 23-51-11 | D41648J | | 8 | | GD01754 | ST.. | 2 | | 001-099 |
| 0197 | 20 | | GA | | 3-0 | 23-51-11 | D41648J | | 8 | | GD01754 | ST.. | 2 | | 115-199 |
| 0198 | 24 | | GK | | 3-1 | 23-51-11 | D41648J | | 7 | | GD01754 | ST.. | 2 | | 001-099 |
| 0198 | 24 | | GK | | 3-0 | 23-51-11 | D41648J | | 7 | | GD01754 | ST.. | 2 | | 115-199 |
| 0199 | 24 | | GK | | 3-2 | 23-51-11 | D00005B | | B03 | | TB0141Y | C010 | BJ | | 001-099 |
| 0199 | 24 | | GK | | 3-0 | 23-51-11 | D00005B | | B03 | | TB0141Y | C010 | BJ | | 115-199 |
| 0200 | 24 | | GK | | 3-4 | 23-51-11 | D00005B | | A04 | | TB0141Y | A013 | BJ | | 001-099 |
| 0200 | 24 | | GK | | 3-0 | 23-51-11 | D00005B | | A04 | | TB0141Y | A013 | BJ | | 115-199 |
| 0201 | 24 | | GK | | 3-0 | 23-51-11 | D41553J | | 5 | | TB0141Y | C010 | BJ | | ALL |
| 0202 | 24 | | GK | | 3-1 | 23-51-11 | D41553J | | 6 | | TB0141Y | A013 | BJ | | 001-099 |
| 0202 | 24 | | GK | | 3-0 | 23-51-11 | D41553J | | 6 | | TB0141Y | A013 | BJ | | 115-199 |
| 0203 | 24 | | GK | | 3-4 | 23-51-11 | D00005A | | CAP | Y | TB0141Y | A010 | BJ | | 001-099 |
| 0203 | 24 | | GK | | 3-0 | 23-51-11 | D00005A | | B06 | | TB0141Y | A010 | BJ | | 115-199 |
| 0204 | 24 | | GK | | 3-4 | 23-51-11 | D00005A | | B07 | | TB0141Z | 11 | BJ | | 001-099 |
| 0204 | 24 | | GK | | 3-0 | 23-51-11 | D00005A | | B07 | | TB0141Z | 11 | BJ | | 115-199 |
| 0205 | 24 | | GK | | 3-0 | 23-51-11 | D41553J | | 3 | | TB0141Y | A010 | BJ | | ALL |
| 0206 | 24 | | GK | | 3-0 | 23-51-11 | D41553J | | 2 | | TB0141Z | 11 | BJ | | 001-099 |
| 0206 | 24 | | GK | | 4-0 | 23-51-11 | D41553J | | 2 | | TB0141Z | 11 | BJ | | 115-199 |
| 0207 | 22 | | GA | | 2-7 | 23-51-11 | D41553J | | 1 | | GD01754 | ST.. | 2 | | 001-099 |
| 0207 | 22 | | GA | | 3-0 | 23-51-11 | D41553J | | 1 | | GD01754 | ST.. | 2 | | 115-199 |
| 0208 | 22 | | GA | | 2-7 | 23-51-11 | D41553J | | 4 | | GD01754 | ST.. | 2 | | 001-099 |
| 0208 | 22 | | GA | | 3-0 | 23-51-11 | D41553J | | 4 | | GD01754 | ST.. | 2 | | 115-199 |
| 0209 | 24 | | GK | | 2-7 | 23-51-11 | D00007B | | B01 | | GD01753 | ST.. | 2 | | 001-099 |
| 0209 | 24 | | GK | | 3-0 | 23-51-11 | D00007B | | B01 | | GD01753 | ST.. | 2 | | 115-199 |
| 0210 | 24 | | GK | | 3-0 | 23-51-11 | D00007B | | A01 | | TB0141Z | 12 | BJ | | ALL |
| 0211 | 24 | | GK | | 3-1 | 23-51-11 | D00007B | | C01 | | TB0141Z | 7 | BJ | | 001-099 |
| 0211 | 24 | | GK | | 3-0 | 23-51-11 | D00007B | | C01 | | TB0141Z | 7 | BJ | | 115-199 |
| 0212 | 24 | | GK | | 2-7 | 23-51-11 | D00007B | | B14 | | GD01753 | ST.. | 2 | | 001-099 |
| 0212 | 24 | | GK | | 3-0 | 23-51-11 | D00007B | | B14 | | GD01753 | ST.. | 2 | | 115-199 |
| 0213 | 24 | | GK | | 3-1 | 23-51-11 | D00007B | | A14 | | TB0141Z | 8 | BJ | | 001-099 |
| 0213 | 24 | | GK | | 3-0 | 23-51-11 | D00007B | | A14 | | TB0141Z | 8 | BJ | | 115-199 |
| 0214 | 24 | | GK | | 3-0 | 23-51-11 | D41553J | | 18 | | TB0141Z | 12 | BJ | | 001-099 |
| 0214 | 24 | | GK | | 4-0 | 23-51-11 | D41553J | | 18 | | TB0141Z | 12 | BJ | | 115-199 |
| 0215 | 24 | | GK | | 3-1 | 23-51-11 | D41553J | | 19 | | TB0141Z | 7 | BJ | | 001-099 |
| 0215 | 24 | | GK | | 4-0 | 23-51-11 | D41553J | | 19 | | TB0141Z | 7 | BJ | | 115-199 |
| 0216 | 24 | | GK | | 3-1 | 23-51-11 | D41553J | | 26 | | TB0141Z | 8 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 10

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | |
| 0216 | 24 | GK | | | 4-0 | 23-51-11 | D41553J | | 26 | | TB0141Z | 8 | BJ | | 115-199 |
| 0217 | 24 | GK | | | 3-2 | 23-51-11 | D00129B | | B01 | | GD01753 | ST.. | 2 | | 001-099 |
| 0217 | 24 | GK | | | 3-0 | 23-51-11 | D00129B | | B01 | | GD01753 | ST.. | 2 | | 115-199 |
| 0218 | 24 | GK | | | 3-8 | 23-51-11 | D00129B | | A01 | | TB0141Z | 15 | BJ | | 001-099 |
| 0218 | 24 | GK | | | 3-0 | 23-51-11 | D00129B | | A01 | | TB0141Z | 15 | BJ | | 115-199 |
| 0219 | 24 | GK | | | 3-8 | 23-51-11 | D00129B | | C01 | | TB0141Z | 2 | BJ | | 001-099 |
| 0219 | 24 | GK | | | 3-0 | 23-51-11 | D00129B | | C01 | | TB0141Z | 2 | BJ | | 115-199 |
| 0220 | 24 | GK | | | 3-2 | 23-51-11 | D00129B | | B15 | | GD01753 | ST.. | 2 | | 001-099 |
| 0220 | 24 | GK | | | 3-0 | 23-51-11 | D00129B | | B15 | | GD01753 | ST.. | 2 | | 115-199 |
| 0221 | 24 | GK | | | 3-8 | 23-51-11 | D00129B | | A15 | | TB0141Z | 16 | BJ | | 001-099 |
| 0221 | 24 | GK | | | 3-0 | 23-51-11 | D00129B | | A15 | | TB0141Z | 16 | BJ | | 115-199 |
| 0222 | 24 | GK | | | 3-1 | 23-51-11 | D41553J | | 16 | | TB0141Z | 15 | BJ | | 001-099 |
| 0222 | 24 | GK | | | 4-0 | 23-51-11 | D41553J | | 16 | | TB0141Z | 15 | BJ | | 115-199 |
| 0223 | 24 | GK | | | 3-1 | 23-51-11 | D41553J | | 17 | | TB0141Z | 2 | BJ | | 001-099 |
| 0223 | 24 | GK | | | 4-0 | 23-51-11 | D41553J | | 17 | | TB0141Z | 2 | BJ | | 115-199 |
| 0224 | 24 | GK | | | 3-1 | 23-51-11 | D41553J | | 25 | | TB0141Z | 16 | BJ | | 001-099 |
| 0224 | 24 | GK | | | 4-0 | 23-51-11 | D41553J | | 25 | | TB0141Z | 16 | BJ | | 115-199 |
| 0225 | 24 | GK | | | 3-9 | 23-51-11 | D00125B | | B01 | | GD01753 | ST.. | 2 | | 001-099 |
| 0225 | 24 | GK | | | 4-0 | 23-51-11 | D00125B | | B01 | | GD01753 | ST.. | 2 | | 115-199 |
| 0226 | 24 | GK | | | 3-9 | 23-51-11 | D00125B | | A01 | | TB0141Z | 17 | BJ | | 001-099 |
| 0226 | 24 | GK | | | 4-0 | 23-51-11 | D00125B | | A01 | | TB0141Z | 17 | BJ | | 115-199 |
| 0227 | 24 | GK | | | 4-3 | 23-51-11 | D00125B | | C01 | | TB0141Z | 1 | BJ | | 001-099 |
| 0227 | 24 | GK | | | 4-0 | 23-51-11 | D00125B | | C01 | | TB0141Z | 1 | BJ | | 115-199 |
| 0228 | 24 | GK | | | 3-9 | 23-51-11 | D00125B | | B15 | | GD01754 | ST.. | 2 | | 001-099 |
| 0228 | 24 | GK | | | 4-0 | 23-51-11 | D00125B | | B15 | | GD01754 | ST.. | 2 | | 115-199 |
| 0229 | 24 | GK | | | 3-9 | 23-51-11 | D00125B | | A15 | | TB0141Z | 18 | BJ | | 001-099 |
| 0229 | 24 | GK | | | 4-0 | 23-51-11 | D00125B | | A15 | | TB0141Z | 18 | BJ | | 115-199 |
| 0230 | 24 | GK | | | 2-7 | 23-51-11 | D41553J | | 8 | | TB0141Z | 17 | BJ | | 001-099 |
| 0230 | 24 | GK | | | 4-0 | 23-51-11 | D41553J | | 8 | | TB0141Z | 17 | BJ | | 115-199 |
| 0231 | 24 | GK | | | 3-1 | 23-51-11 | D41553J | | 9 | | TB0141Z | 1 | BJ | | 001-099 |
| 0231 | 24 | GK | | | 4-0 | 23-51-11 | D41553J | | 9 | | TB0141Z | 1 | BJ | | 115-199 |
| 0232 | 24 | GK | | | 2-7 | 23-51-11 | D41553J | | 21 | | TB0141Z | 18 | BJ | | 001-099 |
| 0232 | 24 | GK | | | 4-0 | 23-51-11 | D41553J | | 21 | | TB0141Z | 18 | BJ | | 115-199 |
| 0233 | 22 | GA | | | 2-11 | 23-51-11 | D00005A | | B01 | | GD01754 | ST.. | 2 | | 001-099 |
| 0233 | 22 | GA | | | 3-0 | 23-51-11 | D00005A | | B01 | | GD01754 | ST.. | 2 | | 115-199 |
| 0234 | 24 | GK | | | 2-5 | 23-51-12 | D41371J | | 5 | | TB0141Z | 19 | BJ | | 001-099 |
| 0234 | 24 | GK | | | 4-0 | 23-51-12 | D41371J | | 5 | | TB0141Z | 19 | BJ | | 115-199 |
| 0235 | 24 | GK | | | 2-5 | 23-51-12 | D41371J | | 6 | | TB0141Z | 20 | BJ | | 001-099 |
| 0235 | 24 | GK | | | 4-0 | 23-51-12 | D41371J | | 6 | | TB0141Z | 20 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 11

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0236 | 24 | | GK | | 2-7 | 23-51-12 | D41553J | | 35 | | TB0141Z | 19 | BJ | | 001-099 |
| 0236 | 24 | | GK | | 4-0 | 23-51-12 | D41553J | | 35 | | TB0141Z | 19 | BJ | | 115-199 |
| 0237 | 24 | | GK | | 2-7 | 23-51-12 | D41553J | | 36 | | TB0141Z | 20 | BJ | | 001-099 |
| 0237 | 24 | | GK | | 4-0 | 23-51-12 | D41553J | | 36 | | TB0141Z | 20 | BJ | | 115-199 |
| 0238 | 24 | | GK | | 3-0 | 23-51-12 | D41371J | | 7 | | GD01755 | ST.. | 2 | | ALL |
| 0239 | 20 | | GA | | 3-0 | 23-51-12 | D41371J | | 8 | | GD01755 | ST.. | 2 | | ALL |
| 0240 | 20 | | GA | | 3-0 | 23-51-12 | D41371J | | 52 | | GD01755 | ST.. | 2 | | 001-099 |
| 0240 | 24 | | GK | | 3-0 | 23-51-12 | D41687J | | 5 | | GD01755 | ST.. | 2 | | 115-199 |
| 0241 | 24 | | GK | | 3-0 | 23-51-12 | D41371J | | 51 | | GD01755 | ST.. | 2 | | 001-099 |
| 0241 | 24 | | GK | | 3-0 | 23-51-12 | D41687J | | 3 | | GD01755 | ST.. | 2 | | 115-199 |
| 0242 | 24 | | GK | | 2-5 | 23-51-12 | D41371J | | 50 | | TB0141Z | 21 | BJ | | 001-099 |
| 0242 | 24 | | GK | | 4-0 | 23-51-12 | D41687J | | 4 | | TB0141Z | 21 | BJ | | 115-199 |
| 0243 | 24 | | GK | | 2-7 | 23-51-12 | D41553J | | 37 | | TB0141Z | 21 | BJ | | 001-099 |
| 0243 | 24 | | GK | | 4-0 | 23-51-12 | D41553J | | 37 | | TB0141Z | 21 | BJ | | 115-199 |
| 0244 | 20 | | GA | | 3-3 | 23-51-12 | D41319J | | 30 | | GD01755 | ST.. | 2 | | 001-099 |
| 0244 | 24 | | GK | | 3-0 | 23-51-12 | D41689J | | 6 | | GD01755 | ST.. | 2 | | 115-199 |
| 0245 | 24 | | GK | | 2-8 | 23-51-12 | D41319J | | 28 | | TB0141Z | 25 | BJ | | 001-099 |
| 0245 | 24 | | GK | | 3-0 | 23-51-12 | D41689J | | 4 | | GD01755 | ST.. | 2 | | 115-199 |
| 0246 | 24 | | GK | | 2-8 | 23-51-12 | D41553J | | 29 | | TB0141Z | 25 | BJ | | 001-099 |
| 0246 | 24 | | GK | | 4-0 | 23-51-12 | D41553J | | 29 | | TB0141Z | 25 | BJ | | 115-199 |
| 0247 | 24 | | GK | | 3-3 | 23-51-12 | D41319J | | 29 | | GD01755 | ST.. | 2 | | 001-099 |
| 0247 | 24 | | GK | | 4-0 | 23-51-12 | D41689J | | 5 | | TB0141Z | 25 | BJ | | 115-199 |
| 0248 | 24 | | GK | | 3-3 | 23-51-12 | D41319J | | 52 | | GD01755 | ST.. | 2 | | 001-099 |
| 0248 | 24 | | GK | | 3-0 | 23-51-12 | D41689J | | 7 | | GD01755 | ST.. | 2 | | 115-199 |
| 0249 | 24 | | GK | | 2-8 | 23-51-12 | D41319J | | 51 | | TB0141Z | 24 | BJ | | 001-099 |
| 0249 | 24 | | GK | | 4-0 | 23-51-12 | D41689J | | 8 | | TB0141Z | 24 | BJ | | 115-199 |
| 0250 | 24 | | GK | | 2-7 | 23-51-12 | D41553J | | 27 | | TB0141Z | 24 | BJ | | 001-099 |
| 0250 | 24 | | GK | | 4-0 | 23-51-12 | D41553J | | 27 | | TB0141Z | 24 | BJ | | 115-199 |
| 0251 | 20 | | GA | | 3-3 | 23-51-12 | D41319J | | 53 | | GD01755 | ST.. | 2 | | 001-099 |
| 0251 | 20 | | GA | | 3-0 | 23-51-12 | D41689J | | 9 | | GD01755 | ST.. | 2 | | 115-199 |
| 0252 | 20 | | GA | | 3-3 | 23-51-12 | D41319J | | 13 | | GD01755 | ST.. | 2 | | 001-099 |
| 0252 | 20 | | GA | | 3-0 | 23-51-12 | D41319J | | 13 | | GD01755 | ST.. | 2 | | 115-199 |
| 0253 | 24 | | GK | | 3-3 | 23-51-12 | D41319J | | 10 | | GD01755 | ST.. | 2 | | 001-099 |
| 0253 | 24 | | GK | | 3-0 | 23-51-12 | D41319J | | 10 | | GD01755 | ST.. | 2 | | 115-199 |
| 0254 | 24 | | GK | | 2-8 | 23-51-12 | D41319J | | 11 | | TB0141Z | 23 | BJ | | 001-099 |
| 0254 | 24 | | GK | | 4-0 | 23-51-12 | D41319J | | 11 | | TB0141Z | 23 | BJ | | 115-199 |
| 0255 | 24 | | GK | | 2-8 | 23-51-12 | D41319J | | 12 | | TB0141Z | 22 | BJ | | 001-099 |
| 0255 | 24 | | GK | | 4-0 | 23-51-12 | D41319J | | 12 | | TB0141Z | 22 | BJ | | 115-199 |
| 0256 | 24 | | GK | | 2-7 | 23-51-12 | D41553J | | 31 | | TB0141Z | 22 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 12

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0256 | 24 | | GK | | 4-0 | 23-51-12 | D41553J | | 31 | | TB0141Z | 22 | BJ | | 115-199 |
| 0257 | 24 | | GK | | 2-7 | 23-51-12 | D41553J | | 30 | | TB0141Z | 23 | BJ | | 001-099 |
| 0257 | 24 | | GK | | 4-0 | 23-51-12 | D41553J | | 30 | | TB0141Z | 23 | BJ | | 115-199 |
| 0258 | 20 | | GA | | 3-5 | 23-51-13 | D41371J | | 15 | | GD01756 | ST.. | 2 | | 001-099 |
| 0258 | 20 | | GA | | 3-0 | 23-51-13 | D41371J | | 15 | | GD01756 | ST.. | 2 | | 115-199 |
| 0259 | 24 | | GK | | 2-5 | 23-51-13 | D41371J | | 13 | | TB0141Z | 26 | BJ | | 001-099 |
| 0259 | 24 | | GK | | 4-0 | 23-51-13 | D41371J | | 13 | | TB0141Z | 26 | BJ | | 115-199 |
| 0260 | 24 | | GK | | 3-5 | 23-51-13 | D41371J | | 14 | | GD01756 | ST.. | 2 | | 001-099 |
| 0260 | 24 | | GK | | 3-0 | 23-51-13 | D41371J | | 14 | | GD01756 | ST.. | 2 | | 115-199 |
| 0261 | 20 | | GA | | 2-7 | 23-51-13 | D41453J | | 34 | | GD01756 | ST.. | 2 | | 001-099 |
| 0261 | 20 | | GA | | 3-0 | 23-51-13 | D41453J | | 34 | | GD01756 | ST.. | 2 | | 115-199 |
| 0262 | 24 | | GK | | 3-3 | 23-51-13 | D41453J | | 35 | | TB0141Z | 27 | BJ | | 001-099 |
| 0262 | 24 | | GK | | 3-0 | 23-51-13 | D41453J | | 35 | | TB0141Z | 27 | BJ | | 115-199 |
| 0263 | 24 | | GK | | 2-7 | 23-51-13 | D41453J | | 33 | | GD01756 | ST.. | 2 | | 001-099 |
| 0263 | 24 | | GK | | 3-0 | 23-51-13 | D41453J | | 33 | | GD01756 | ST.. | 2 | | 115-199 |
| 0264 | 20 | | GA | | 3-8 | 23-51-13 | D41319J | | 9 | | GD01756 | ST.. | 2 | | 001-099 |
| 0264 | 20 | | GA | | 3-0 | 23-51-13 | D41319J | | 7 | | GD01756 | ST.. | 2 | | 115-199 |
| 0265 | 24 | | GK | | 2-8 | 23-51-13 | D41319J | | 7 | | TB0141Z | 28 | BJ | | 001-099 |
| 0265 | 24 | | GK | | 4-0 | 23-51-13 | D41319J | | 8 | | TB0141Z | 28 | BJ | | 115-199 |
| 0266 | 24 | | GK | | 3-8 | 23-51-13 | D41319J | | 8 | | GD01756 | ST.. | 2 | | 001-099 |
| 0266 | 24 | | GK | | 3-0 | 23-51-13 | D41319J | | 9 | | GD01756 | ST.. | 2 | | 115-199 |
| 0267 | 20 | | GA | | 3-8 | 23-51-13 | D41319J | | 27 | | GD01756 | ST.. | 2 | | 001-099 |
| 0267 | 20 | | GA | | 3-0 | 23-51-13 | D41689J | | 12 | | GD01756 | ST.. | 2 | | 115-199 |
| 0268 | 24 | | GK | | 2-9 | 23-51-13 | D41319J | | 25 | | TB0141Z | 29 | BJ | | 001-099 |
| 0268 | 24 | | GK | | 4-0 | 23-51-13 | D41689J | | 11 | | TB0141Z | 29 | BJ | | 115-199 |
| 0269 | 24 | | GK | | 3-8 | 23-51-13 | D41319J | | 26 | | GD01756 | ST.. | 2 | | 001-099 |
| 0269 | 24 | | GK | | 3-0 | 23-51-13 | D41689J | | 10 | | GD01756 | ST.. | 2 | | 115-199 |
| 0270 | 24 | | GK | | 2-11 | 23-51-13 | D41561J | | 17 | | GD01756 | ST.. | 2 | | 001-099 |
| 0270 | 24 | | GK | | 4-0 | 23-51-13 | D41561J | | 17 | | GD01756 | ST.. | 2 | | 115-199 |
| 0271 | 24 | | GK | | 2-5 | 23-51-13 | D41553J | | 7 | | D41561J | 7 | | | 001-099 |
| 0271 | 24 | | GK | | 3-0 | 23-51-13 | D41553J | | 7 | | D41561J | 7 | | | 115-199 |
| 0272 | 24 | | GK | | 2-8 | 23-51-13 | D41553J | | 34 | | TB0141Z | 26 | BJ | | 001-099 |
| 0272 | 24 | | GK | | 4-0 | 23-51-13 | D41553J | | 34 | | TB0141Z | 26 | BJ | | 115-199 |
| 0273 | 24 | | GK | | 2-8 | 23-51-13 | D41553J | | 33 | | TB0141Z | 27 | BJ | | 001-099 |
| 0273 | 24 | | GK | | 4-0 | 23-51-13 | D41553J | | 33 | | TB0141Z | 27 | BJ | | 115-199 |
| 0274 | 24 | | GK | | 2-8 | 23-51-13 | D41553J | | 32 | | TB0141Z | 28 | BJ | | 001-099 |
| 0274 | 24 | | GK | | 4-0 | 23-51-13 | D41553J | | 32 | | TB0141Z | 28 | BJ | | 115-199 |
| 0275 | 24 | | GK | | 2-6 | 23-51-13 | D41553J | | 28 | | TB0141Z | 29 | BJ | | 001-099 |
| 0275 | 24 | | GK | | 4-0 | 23-51-13 | D41553J | | 28 | | TB0141Z | 29 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 13

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0276 | 20 | | GA | | 3-5 | 23-51-13 | D41371J | | 55 | | GD01756 | ST.. | 2 | | 001-099 |
| 0276 | 20 | | GA | | 3-0 | 23-51-13 | D41687J | | 8 | | GD01756 | ST.. | 2 | | 115-199 |
| 0277 | 24 | | GK | | 2-6 | 23-51-13 | D41371J | | 53 | | TB0141Z | 39 | BJ | | 001-099 |
| 0277 | 24 | | GK | | 4-0 | 23-51-13 | D41687J | | 7 | | TB0141Z | 39 | BJ | | 115-199 |
| 0278 | 20 | | GA | | 3-5 | 23-51-13 | D41371J | | 54 | | GD01756 | ST.. | 2 | | 001-099 |
| 0278 | 20 | | GA | | 3-0 | 23-51-13 | D41687J | | 6 | | GD01756 | ST.. | 2 | | 115-199 |
| 0279 | 24 | | GK | | 2-6 | 23-51-13 | D41553J | | 38 | | TB0141Z | 39 | BJ | | 001-099 |
| 0279 | 24 | | GK | | 4-0 | 23-51-13 | D41553J | | 38 | | TB0141Z | 39 | BJ | | 115-199 |
| 0280 | 24 | | GK | | 2-6 | 23-51-14 | D41371J | | 42 | | TB0141Z | 4 | BJ | | 001-099 |
| 0280 | 24 | | GK | | 4-0 | 23-51-14 | D41687J | | 9 | | TB0141Z | 4 | BJ | | 115-199 |
| 0281 | 24 | | GK | | 3-1 | 23-51-14 | D41553J | | 15 | | TB0141Z | 4 | BJ | | 001-099 |
| 0281 | 24 | | GK | | 4-0 | 23-51-14 | D41553J | | 15 | | TB0141Z | 4 | BJ | | 115-199 |
| 0282 | 24 | | GK | | 3-4 | 23-51-14 | D41371J | | 45 | | GD01757 | ST.. | 2 | | 001-099 |
| 0282 | 20 | | GA | | 5-0 | 23-51-14 | D41687J | | 13 | | GD01757 | ST.. | 2 | | 115-199 |
| 0283 | 24 | | GK | | 2-6 | 23-51-14 | D41371J | | 44 | | TB0141Z | 30 | BJ | | 001-099 |
| 0283 | 24 | | GK | | 4-0 | 23-51-14 | D41687J | | 14 | | TB0141Z | 30 | BJ | | 115-199 |
| 0284 | 24 | | GK | | 2-6 | 23-51-14 | D41553J | | 14 | | TB0141Z | 30 | BJ | | 001-099 |
| 0284 | 24 | | GK | | 4-0 | 23-51-14 | D41553J | | 14 | | TB0141Z | 30 | BJ | | 115-199 |
| 0285 | 24 | | GK | | 2-6 | 23-51-14 | D41371J | | 47 | | TB0141Z | 31 | BJ | | 001-099 |
| 0285 | 24 | | GK | | 4-0 | 23-51-14 | D41687J | | 17 | | TB0141Z | 31 | BJ | | 115-199 |
| 0286 | 24 | | GK | | 2-6 | 23-51-14 | D41553J | | 24 | | TB0141Z | 31 | BJ | | 001-099 |
| 0286 | 24 | | GK | | 4-0 | 23-51-14 | D41553J | | 24 | | TB0141Z | 31 | BJ | | 115-199 |
| 0287 | 24 | | GK | | 3-4 | 23-51-14 | D41371J | | 48 | | GD01757 | ST.. | 2 | | 001-099 |
| 0287 | 20 | | GA | | 5-0 | 23-51-14 | D41687J | | 16 | | GD01757 | ST.. | 2 | | 115-199 |
| 0288 | 20 | | GA | | 2-7 | 23-51-14 | D41553J | | 20 | | GD01757 | ST.. | 2 | | 001-099 |
| 0288 | 20 | | GA | | 3-0 | 23-51-14 | D41553J | | 20 | | GD01757 | ST.. | 2 | | 115-199 |
| 0289 | 24 | | GK | | 3-0 | 23-51-14 | D41689J | | 16 | | GD01757 | ST.. | 2 | | 115-199 |
| 0290 | 24 | | GK | | 4-0 | 23-51-14 | D41689J | | 17 | | TB0141Z | 32 | BJ | | 115-199 |
| 0291 | 24 | | GK | | 2-11 | 23-51-14 | D41553J | | 22 | | TB0141Z | 68 | BJ | | 001-099 |
| 0291 | 24 | | GK | | 4-0 | 23-51-14 | D41553J | | 22 | | TB0141Z | 32 | BJ | | 115-199 |
| 0292 | 24 | | GK | | 3-0 | 23-51-14 | D41689J | | 13 | | GD01757 | ST.. | 2 | | 115-199 |
| 0293 | 24 | | GK | | 4-0 | 23-51-14 | D41689J | | 14 | | TB0141Z | 33 | BJ | | 115-199 |
| 0294 | 24 | | GK | | 2-11 | 23-51-14 | D41553J | | 10 | | TB0141Z | 69 | BJ | | 001-099 |
| 0294 | 24 | | GK | | 4-0 | 23-51-14 | D41553J | | 10 | | TB0141Z | 33 | BJ | | 115-199 |
| 0295 | 24 | | GK | | 4-0 | 23-51-14 | D41689J | | 3 | | TB0141Z | 3 | BJ | | 115-199 |
| 0296 | 24 | | GK | | 3-1 | 23-51-14 | D41553J | | 11 | | TB0141Z | 3 | BJ | | 001-099 |
| 0296 | 24 | | GK | | 4-0 | 23-51-14 | D41553J | | 11 | | TB0141Z | 3 | BJ | | 115-199 |
| 0297 | 24 | | GK | | 2-8 | 23-51-21 | D41555J | | 3 | | D00005A | B03 | | | 001-099 |
| 0297 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 3 | | D00005A | B03 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 14

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0298 | 24 | | GK | | 3-1 | 23-51-21 | D41555J | | 2 | | TB0141Z | 11 | BJ | | 001-099 |
| 0298 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 2 | | TB0141Z | 11 | BJ | | 115-199 |
| 0299 | 24 | | GK | | 2-7 | 23-51-21 | D41555J | | 5 | | D00005B | B04 | | | 001-099 |
| 0299 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 5 | | D00005B | B04 | | | 115-199 |
| 0300 | 24 | | GK | | 2-8 | 23-51-21 | D41555J | | 6 | | TB0141Y | C037 | BJ | | 001-099 |
| 0300 | 24 | | GK | | 3-0 | 23-51-21 | D41555J | | 6 | | TB0141Y | C037 | BJ | | 115-199 |
| 0301 | 24 | | GK | | 2-9 | 23-51-21 | D00005B | A05 | | | TB0141Y | C037 | BJ | | 001-099 |
| 0301 | 24 | | GK | | 3-0 | 23-51-21 | D00005B | A05 | | | TB0141Y | C037 | BJ | | 115-199 |
| 0302 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 4 | | GD01757 | ST.. | 2 | | 001-099 |
| 0302 | 24 | | GK | | 3-0 | 23-51-21 | D41555J | | 4 | | GD01757 | ST.. | 2 | | 115-199 |
| 0303 | 20 | | GA | | 2-9 | 23-51-21 | D41555J | | 20 | | GD01757 | ST.. | 2 | | 001-099 |
| 0303 | 20 | | GA | | 3-0 | 23-51-21 | D41555J | | 20 | | GD01757 | ST.. | 2 | | 115-199 |
| 0304 | 24 | | GK | | 3-1 | 23-51-21 | D41555J | | 18 | | TB0141Z | 12 | BJ | | 001-099 |
| 0304 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 18 | | TB0141Z | 12 | BJ | | 115-199 |
| 0305 | 24 | | GK | | 3-2 | 23-51-21 | D41555J | | 19 | | TB0141Z | 7 | BJ | | 001-099 |
| 0305 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 19 | | TB0141Z | 7 | BJ | | 115-199 |
| 0306 | 24 | | GK | | 3-2 | 23-51-21 | D41555J | | 26 | | TB0141Z | 8 | BJ | | 001-099 |
| 0306 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 26 | | TB0141Z | 8 | BJ | | 115-199 |
| 0307 | 24 | | GK | | 3-2 | 23-51-21 | D41555J | | 16 | | TB0141Z | 15 | BJ | | 001-099 |
| 0307 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 16 | | TB0141Z | 15 | BJ | | 115-199 |
| 0308 | 24 | | GK | | 3-2 | 23-51-21 | D41555J | | 17 | | TB0141Z | 2 | BJ | | 001-099 |
| 0308 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 17 | | TB0141Z | 2 | BJ | | 115-199 |
| 0309 | 24 | | GK | | 3-2 | 23-51-21 | D41555J | | 25 | | TB0141Z | 16 | BJ | | 001-099 |
| 0309 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 25 | | TB0141Z | 16 | BJ | | 115-199 |
| 0310 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 8 | | TB0141Z | 17 | BJ | | 001-099 |
| 0310 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 8 | | TB0141Z | 17 | BJ | | 115-199 |
| 0311 | 24 | | GK | | 3-2 | 23-51-21 | D41555J | | 9 | | TB0141Z | 1 | BJ | | 001-099 |
| 0311 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 9 | | TB0141Z | 1 | BJ | | 115-199 |
| 0312 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 21 | | TB0141Z | 18 | BJ | | 001-099 |
| 0312 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 21 | | TB0141Z | 18 | BJ | | 115-199 |
| 0313 | 24 | | GK | | 2-8 | 23-51-21 | D41555J | | 14 | | TB0141Z | 30 | BJ | | 001-099 |
| 0313 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 14 | | TB0141Z | 30 | BJ | | 115-199 |
| 0314 | 24 | | GK | | 3-2 | 23-51-21 | D41555J | | 15 | | TB0141Z | 4 | BJ | | 001-099 |
| 0314 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 15 | | TB0141Z | 4 | BJ | | 115-199 |
| 0315 | 24 | | GK | | 2-8 | 23-51-21 | D41555J | | 24 | | TB0141Z | 31 | BJ | | 001-099 |
| 0315 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 24 | | TB0141Z | 31 | BJ | | 115-199 |
| 0316 | 24 | | GK | | 3-0 | 23-51-21 | D41555J | | 10 | | TB0141Z | 69 | BJ | | 001-099 |
| 0316 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 10 | | TB0141Z | 33 | BJ | | 115-199 |
| 0317 | 24 | | GK | | 3-2 | 23-51-21 | D41555J | | 11 | | TB0141Z | 3 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 15

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0317 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 11 | | TB0141Z | 3 | BJ | | 115-199 |
| 0318 | 24 | | GK | | 3-0 | 23-51-21 | D41555J | | 22 | | TB0141Z | 68 | BJ | | 001-099 |
| 0318 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 22 | | TB0141Z | 32 | BJ | | 115-199 |
| 0319 | 24 | | GK | | 2-8 | 23-51-21 | D41555J | | 38 | | TB0141Z | 39 | BJ | | 001-099 |
| 0319 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 38 | | TB0141Z | 39 | BJ | | 115-199 |
| 0320 | 24 | | GK | | 2-8 | 23-51-21 | D41555J | | 28 | | TB0141Z | 29 | BJ | | 001-099 |
| 0320 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 28 | | TB0141Z | 29 | BJ | | 115-199 |
| 0321 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 34 | | TB0141Z | 26 | BJ | | 001-099 |
| 0321 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 34 | | TB0141Z | 26 | BJ | | 115-199 |
| 0322 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 33 | | TB0141Z | 27 | BJ | | 001-099 |
| 0322 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 33 | | TB0141Z | 27 | BJ | | 115-199 |
| 0323 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 32 | | TB0141Z | 28 | BJ | | 001-099 |
| 0323 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 32 | | TB0141Z | 28 | BJ | | 115-199 |
| 0324 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 36 | | TB0141Z | 20 | BJ | | 001-099 |
| 0324 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 36 | | TB0141Z | 20 | BJ | | 115-199 |
| 0325 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 30 | | TB0141Z | 23 | BJ | | 001-099 |
| 0325 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 30 | | TB0141Z | 23 | BJ | | 115-199 |
| 0326 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 37 | | TB0141Z | 21 | BJ | | 001-099 |
| 0326 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 37 | | TB0141Z | 21 | BJ | | 115-199 |
| 0327 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 29 | | TB0141Z | 25 | BJ | | 001-099 |
| 0327 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 29 | | TB0141Z | 25 | BJ | | 115-199 |
| 0328 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 35 | | TB0141Z | 19 | BJ | | 001-099 |
| 0328 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 35 | | TB0141Z | 19 | BJ | | 115-199 |
| 0329 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 31 | | TB0141Z | 22 | BJ | | 001-099 |
| 0329 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 31 | | TB0141Z | 22 | BJ | | 115-199 |
| 0330 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 27 | | TB0141Z | 24 | BJ | | 001-099 |
| 0330 | 24 | | GK | | 4-0 | 23-51-21 | D41555J | | 27 | | TB0141Z | 24 | BJ | | 115-199 |
| 0331 | 24 | | GK | | 2-11 | 23-51-21 | TB0141Z | | 34 | BJ | GD01757 | ST.. | 2 | | 001-099 |
| 0331 | 24 | | GK | | 3-0 | 23-51-21 | TB0141Z | | 34 | BJ | GD01757 | ST.. | 2 | | 115-199 |
| 0332 | 24 | | GK | | 2-9 | 23-51-21 | D41555J | | 1 | | GD01757 | ST.. | 2 | | 001-099 |
| 0332 | 24 | | GK | | 3-0 | 23-51-21 | D41555J | | 1 | | GD01757 | ST.. | 2 | | 115-199 |
| 0333 | 24 | | GK | | 2-7 | 23-51-21 | D41555J | | 7 | | D41561J | 8 | | | 001-099 |
| 0333 | 24 | | GK | | 3-0 | 23-51-21 | D41555J | | 7 | | D41561J | 8 | | | 115-199 |
| 0334 | 24 | | GK | | 2-9 | 23-51-21 | D41561J | | 2 | | TB0141Z | 34 | BJ | | 001-099 |
| 0334 | 24 | | GK | | 3-0 | 23-51-21 | D41561J | | 2 | | TB0141Z | 34 | BJ | | 115-199 |
| 0335 | 24 | | GK | | 4-0 | 23-51-51 | D41557J | | 3 | | D00005A | B05 | | | 115-199 |
| 0336 | 24 | | GK | | 4-0 | 23-51-51 | D41557J | | 2 | | TB0141Z | 11 | BJ | | 115-199 |
| 0337 | 24 | | GK | | 3-0 | 23-51-51 | D41557J | | 5 | | D00005B | B05 | | | 115-199 |
| 0338 | 24 | | GK | | 3-0 | 23-51-51 | D41557J | | 6 | | TB0141Y | A013 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 16

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1163 | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | | | | |
| 0339 | 22 | | GA | 3-0 | 23-51-51 | D41557J | | 20 | | | GD01758 | ST.. | 2 | | 115-199 | | |
| 0340 | 22 | | GA | 3-0 | 23-51-51 | D41557J | | 4 | | | GD01758 | ST.. | 2 | | 115-199 | | |
| 0341 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 18 | | | TB0141Z | 12 | BJ | | 115-199 | | |
| 0342 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 19 | | | TB0141Z | 7 | BJ | | 115-199 | | |
| 0343 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 26 | | | TB0141Z | 8 | BJ | | 115-199 | | |
| 0344 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 16 | | | TB0141Z | 15 | BJ | | 115-199 | | |
| 0345 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 17 | | | TB0141Z | 2 | BJ | | 115-199 | | |
| 0346 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 25 | | | TB0141Z | 16 | BJ | | 115-199 | | |
| 0347 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 8 | | | TB0141Z | 17 | BJ | | 115-199 | | |
| 0348 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 9 | | | TB0141Z | 1 | BJ | | 115-199 | | |
| 0349 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 21 | | | TB0141Z | 18 | BJ | | 115-199 | | |
| 0350 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 14 | | | TB0141Z | 30 | BJ | | 115-199 | | |
| 0351 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 15 | | | TB0141Z | 4 | BJ | | 115-199 | | |
| 0352 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 24 | | | TB0141Z | 31 | BJ | | 115-199 | | |
| 0353 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 10 | | | TB0141Z | 33 | BJ | | 115-199 | | |
| 0354 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 11 | | | TB0141Z | 3 | BJ | | 115-199 | | |
| 0355 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 22 | | | TB0141Z | 32 | BJ | | 115-199 | | |
| 0356 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 38 | | | TB0141Z | 39 | BJ | | 115-199 | | |
| 0357 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 28 | | | TB0141Z | 29 | BJ | | 115-199 | | |
| 0358 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 34 | | | TB0141Z | 26 | BJ | | 115-199 | | |
| 0359 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 33 | | | TB0141Z | 27 | BJ | | 115-199 | | |
| 0360 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 32 | | | TB0141Z | 28 | BJ | | 115-199 | | |
| 0361 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 36 | | | TB0141Z | 20 | BJ | | 115-199 | | |
| 0362 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 30 | | | TB0141Z | 23 | BJ | | 115-199 | | |
| 0363 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 37 | | | TB0141Z | 21 | BJ | | 115-199 | | |
| 0364 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 29 | | | TB0141Z | 25 | BJ | | 115-199 | | |
| 0365 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 35 | | | TB0141Z | 19 | BJ | | 115-199 | | |
| 0366 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 31 | | | TB0141Z | 22 | BJ | | 115-199 | | |
| 0367 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 27 | | | TB0141Z | 24 | BJ | | 115-199 | | |
| 0368 | 24 | | GK | 4-0 | 23-51-51 | D41557J | | 1 | | | TB0141Z | 34 | BJ | | 115-199 | | |
| 0369 | 24 | | GK | 2-7 | 23-51-41 | D41559J | | 7 | | | D41561J | 18 | | | 001-099 | | |
| 0369 | 24 | | GK | 3-0 | 23-51-51 | D41557J | | 7 | | | D41561J | 18 | | | 115-199 | | |
| 0370 | 24 | | GK | 2-9 | 23-51-41 | D41561J | | 19 | | | TB0141Z | 34 | BJ | | 001-099 | | |
| 0370 | 24 | | GK | 3-0 | 23-51-51 | D41561J | | 19 | | | TB0141Z | 34 | BJ | | 115-199 | | |
| 0371 | 24 | | GK | 2-8 | 23-51-41 | D41559J | | 3 | | | D00005A | B04 | | | 001-099 | | |
| 0371 | 24 | | GK | 4-0 | 23-51-41 | D41559J | | 3 | | | D00005A | B04 | | | 115-199 | | |
| 0372 | 24 | | GK | 3-1 | 23-51-41 | D41559J | | 2 | | | TB0141Z | 11 | BJ | | 001-099 | | |
| 0372 | 24 | | GK | 4-0 | 23-51-41 | D41559J | | 2 | | | TB0141Z | 11 | BJ | | 115-199 | | |
| 0373 | 24 | | GK | 2-7 | 23-51-41 | D41559J | | 5 | | | D00005B | B06 | | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 17

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1163 | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | | | | |
| 0373 | 24 | | GK | | 3-0 | 23-51-41 | D41559J | | 5 | | | D00005B | B06 | | | 115-199 | |
| 0374 | 24 | | GK | | 2-8 | 23-51-41 | D41559J | | 6 | | | TB0141Y | C037 | BJ | | 001-099 | |
| 0374 | 24 | | GK | | 3-0 | 23-51-41 | D41559J | | 6 | | | TB0141Y | C037 | BJ | | 115-199 | |
| 0375 | 20 | | GA | | 2-8 | 23-51-41 | D41559J | | 20 | | | GD01758 | ST.. | 2 | | 001-099 | |
| 0375 | 20 | | GA | | 3-0 | 23-51-41 | D41559J | | 20 | | | GD01758 | ST.. | 2 | | 115-199 | |
| 0376 | 24 | | GK | | 2-8 | 23-51-41 | D41559J | | 4 | | | GD01758 | ST.. | 2 | | 001-099 | |
| 0376 | 24 | | GK | | 3-0 | 23-51-41 | D41559J | | 4 | | | GD01758 | ST.. | 2 | | 115-199 | |
| 0377 | 24 | | GK | | 3-1 | 23-51-41 | D41559J | | 18 | | | TB0141Z | 12 | BJ | | 001-099 | |
| 0377 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 18 | | | TB0141Z | 12 | BJ | | 115-199 | |
| 0378 | 24 | | GK | | 3-2 | 23-51-41 | D41559J | | 19 | | | TB0141Z | 7 | BJ | | 001-099 | |
| 0378 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 19 | | | TB0141Z | 7 | BJ | | 115-199 | |
| 0379 | 24 | | GK | | 3-2 | 23-51-41 | D41559J | | 26 | | | TB0141Z | 8 | BJ | | 001-099 | |
| 0379 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 26 | | | TB0141Z | 8 | BJ | | 115-199 | |
| 0380 | 24 | | GK | | 3-2 | 23-51-41 | D41559J | | 16 | | | TB0141Z | 15 | BJ | | 001-099 | |
| 0380 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 16 | | | TB0141Z | 15 | BJ | | 115-199 | |
| 0381 | 24 | | GK | | 3-2 | 23-51-41 | D41559J | | 17 | | | TB0141Z | 2 | BJ | | 001-099 | |
| 0381 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 17 | | | TB0141Z | 2 | BJ | | 115-199 | |
| 0382 | 24 | | GK | | 3-2 | 23-51-41 | D41559J | | 25 | | | TB0141Z | 16 | BJ | | 001-099 | |
| 0382 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 25 | | | TB0141Z | 16 | BJ | | 115-199 | |
| 0383 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | | 8 | | | TB0141Z | 17 | BJ | | 001-099 | |
| 0383 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 8 | | | TB0141Z | 17 | BJ | | 115-199 | |
| 0384 | 24 | | GK | | 3-2 | 23-51-41 | D41559J | | 9 | | | TB0141Z | 1 | BJ | | 001-099 | |
| 0384 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 9 | | | TB0141Z | 1 | BJ | | 115-199 | |
| 0385 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | | 21 | | | TB0141Z | 18 | BJ | | 001-099 | |
| 0385 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 21 | | | TB0141Z | 18 | BJ | | 115-199 | |
| 0386 | 24 | | GK | | 2-8 | 23-51-41 | D41559J | | 14 | | | TB0141Z | 30 | BJ | | 001-099 | |
| 0386 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 14 | | | TB0141Z | 30 | BJ | | 115-199 | |
| 0387 | 24 | | GK | | 3-2 | 23-51-41 | D41559J | | 15 | | | TB0141Z | 4 | BJ | | 001-099 | |
| 0387 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 15 | | | TB0141Z | 4 | BJ | | 115-199 | |
| 0388 | 24 | | GK | | 2-8 | 23-51-41 | D41559J | | 24 | | | TB0141Z | 31 | BJ | | 001-099 | |
| 0388 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 24 | | | TB0141Z | 31 | BJ | | 115-199 | |
| 0389 | 24 | | GK | | 3-0 | 23-51-41 | D41559J | | 10 | | | TB0141Z | 69 | BJ | | 001-099 | |
| 0389 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 10 | | | TB0141Z | 33 | BJ | | 115-199 | |
| 0390 | 24 | | GK | | 3-2 | 23-51-41 | D41559J | | 11 | | | TB0141Z | 3 | BJ | | 001-099 | |
| 0390 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 11 | | | TB0141Z | 3 | BJ | | 115-199 | |
| 0391 | 24 | | GK | | 3-0 | 23-51-41 | D41559J | | 22 | | | TB0141Z | 68 | BJ | | 001-099 | |
| 0391 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 22 | | | TB0141Z | 32 | BJ | | 115-199 | |
| 0392 | 24 | | GK | | 2-8 | 23-51-41 | D41559J | | 38 | | | TB0141Z | 39 | BJ | | 001-099 | |
| 0392 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | | 38 | | | TB0141Z | 39 | BJ | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 18

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0393 | 24 | | GK | | 2-8 | 23-51-41 | D41559J | 28 | | | TB0141Z | 29 | BJ | | 001-099 |
| 0393 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 28 | | | TB0141Z | 29 | BJ | | 115-199 |
| 0394 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 34 | | | TB0141Z | 26 | BJ | | 001-099 |
| 0394 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 34 | | | TB0141Z | 26 | BJ | | 115-199 |
| 0395 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 33 | | | TB0141Z | 27 | BJ | | 001-099 |
| 0395 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 33 | | | TB0141Z | 27 | BJ | | 115-199 |
| 0396 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 32 | | | TB0141Z | 28 | BJ | | 001-099 |
| 0396 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 32 | | | TB0141Z | 28 | BJ | | 115-199 |
| 0397 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 36 | | | TB0141Z | 20 | BJ | | 001-099 |
| 0397 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 36 | | | TB0141Z | 20 | BJ | | 115-199 |
| 0398 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 30 | | | TB0141Z | 23 | BJ | | 001-099 |
| 0398 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 30 | | | TB0141Z | 23 | BJ | | 115-199 |
| 0399 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 37 | | | TB0141Z | 21 | BJ | | 001-099 |
| 0399 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 37 | | | TB0141Z | 21 | BJ | | 115-199 |
| 0400 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 29 | | | TB0141Z | 25 | BJ | | 001-099 |
| 0400 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 29 | | | TB0141Z | 25 | BJ | | 115-199 |
| 0401 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 35 | | | TB0141Z | 19 | BJ | | 001-099 |
| 0401 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 35 | | | TB0141Z | 19 | BJ | | 115-199 |
| 0402 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 31 | | | TB0141Z | 22 | BJ | | 001-099 |
| 0402 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 31 | | | TB0141Z | 22 | BJ | | 115-199 |
| 0403 | 24 | | GK | | 2-9 | 23-51-41 | D41559J | 27 | | | TB0141Z | 24 | BJ | | 001-099 |
| 0403 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 27 | | | TB0141Z | 24 | BJ | | 115-199 |
| 0404 | 24 | | GK | | 2-7 | 23-51-41 | D41559J | 1 | | | TB0141Z | 34 | BJ | | 001-099 |
| 0404 | 24 | | GK | | 4-0 | 23-51-41 | D41559J | 1 | | | TB0141Z | 34 | BJ | | 115-199 |
| 0405 | 20 | | GA | | 3-1 | 23-71-11 | D40672J | 1 | | | D41561J | 1 | | | 001-099 |
| 0405 | 20 | | GA | | 3-0 | 23-71-11 | D40672J | 1 | | | D41561J | 1 | | | 115-199 |
| 0406 | 20 | | GA | | 3-4 | 23-71-11 | D41541J | 21 | | | D41561J | 3 | | | 001-099 |
| 0406 | 20 | | GA | | 4-0 | 23-71-11 | D41541J | 21 | | | D41561J | 3 | | | 115-199 |
| 0407 | 22 | | GA | | 3-4 | 23-71-11 | D41541J | 22 | | | D41561J | 5 | | | 001-099 |
| 0407 | 22 | | GA | | 4-0 | 23-71-11 | D41541J | 22 | | | D41561J | 5 | | | 115-199 |
| 0408 | 24 | | GK | | 3-4 | 23-71-11 | D41541J | 36 | | | D41561J | 6 | | | 001-099 |
| 0408 | 24 | | GK | | 4-0 | 23-71-11 | D41541J | 36 | | | D41561J | 6 | | | 115-199 |
| 0409 | 24 | | GK | | 3-4 | 23-71-11 | D41541J | 37 | | | D41561J | 4 | | | 001-099 |
| 0409 | 24 | | GK | | 4-0 | 23-71-11 | D41541J | 37 | | | D41561J | 4 | | | 115-199 |
| 0410 | 24 | | GK | | 3-4 | 23-71-11 | D41541J | 38 | | | D41561J | 12 | | | 001-099 |
| 0410 | 24 | | GK | | 4-0 | 23-71-11 | D41541J | 38 | | | D41561J | 12 | | | 115-199 |
| 0411 | 24 | | GK | | 3-4 | 23-71-11 | D41541J | 39 | | | D41561J | 11 | | | 001-099 |
| 0411 | 24 | | GK | | 4-0 | 23-71-11 | D41541J | 39 | | | D41561J | 11 | | | 115-199 |
| 0412 | 22 | | GA | | 3-4 | 23-71-11 | D41541J | 26 | | | D41561J | 16 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 19

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0412 | 22 | | GA | | 4-0 | 23-71-11 | D41541J | | 26 | | D41561J | | 16 | | 115-199 |
| 0413 | 22 | | GA | | 3-6 | 23-71-11 | D41319J | | 15 | | D41561J | | 15 | | 001-099 |
| 0413 | 22 | | GA | | 4-0 | 23-71-11 | D41319J | | 15 | | D41561J | | 15 | | 115-199 |
| 0414 | 22 | | GA | | 1-10 | 23-71-11 | D41319J | | 14 | | D41541J | | 27 | | 001-099 |
| 0414 | 22 | | GA | | 3-0 | 23-71-11 | D41319J | | 14 | | D41541J | | 27 | | 115-199 |
| 0415 | 22 | | GA | | 2-7 | 33-25-11 | D00007B | | A11 | | TB0141Y | C038 | BJ | | 001-099 |
| 0415 | 24 | | GK | | 3-0 | 23-31-41 | D41453J | | 12 | | TB0141A | C059 | 2 | | 115-199 |
| 0416 | 22 | | GA | | 3-2 | 33-25-11 | D41453J | | 38 | | TB0141Y | C038 | BJ | | 001-099 |
| 0417 | 22 | | GA | | 3-2 | 33-25-21 | D41453J | | 39 | | TB0141Y | C038 | BJ | | 001-099 |
| 0418 | 24 | | GK | | 4-0 | SPARE | D41371J | | 17 | | TB0141Z | 4 | BJ | | 115-199 |
| 0419 | 24 | | GK | | 2-6 | 23-31-41 | D41453J | | 12 | | TB0141A | C059 | 2 | * | 001-099 |
| 0419 | 24 | | GK | | 4-0 | 31-31-32 | D41319J | | 4 | | TB0141Z | 3 | BJ | | 115-199 |
| 0420 | 24 | | GK | | 4-5 | 31-31-61 | D41319J | | 1 | | D00125B | D01 | | | 001-099 |
| 0420 | 24 | | GK | | 4-0 | 31-31-32 | D41319J | | 1 | | D00125B | D01 | | | 115-199 |
| 0421 | 24 | | GK | | 3-7 | 31-31-61 | D41371J | | 16 | | D00129B | D01 | | | 001-099 |
| 0421 | 24 | | GK | | 3-0 | 31-31-32 | D41371J | | 16 | | D00129B | D01 | | | 115-199 |
| 0422 | 22 | | GA | | 2-10 | 23-12-11 | D00125B | | D03 | | GD01758 | DC.. | 2 | | 001-099 |
| 0422 | 22 | | GA | | 3-0 | 23-12-11 | D00125B | | D03 | | GD01758 | DC.. | 2 | | 115-199 |
| 0423 | 20 | | GA | | 1-6 | 23-12-11 | D41531J | | | AO | GD01759 | ST.. | 2 | | 001-099 |
| 0423 | 20 | | GA | | 1-6 | 23-12-11 | D41531J | | | AO | GD01757 | ST.. | 2 | | 115-199 |
| 0424 | 24 | | GK | | 2-4 | 23-12-11 | D41531J | | 5 | | D00125B | A03 | | | 001-099 |
| 0424 | 24 | | GK | | 4-0 | 23-12-11 | D41531J | | 5 | | D00125B | A03 | | | 115-199 |
| 0425 | 24 | | GK | | 2-4 | 23-12-11 | D41531J | | 6 | | D00125B | B03 | | | 001-099 |
| 0425 | 24 | | GK | | 4-0 | 23-12-11 | D41531J | | 6 | | D00125B | B03 | | | 115-199 |
| 0426 | 24 | | GK | | 2-4 | 23-12-11 | D41531J | | 1 | | D00125B | C03 | | | 001-099 |
| 0426 | 24 | | GK | | 4-0 | 23-12-11 | D41531J | | 1 | | D00125B | C03 | | | 115-199 |
| 0427 | 24 | | GK | | 2-4 | 23-12-11 | D41531J | | 8 | | D00125B | C13 | | | 001-099 |
| 0427 | 24 | | GK | | 4-0 | 23-12-11 | D41531J | | 8 | | D00125B | C13 | | | 115-199 |
| 0428 | 24 | | GK | | 2-4 | 23-12-11 | D41531J | | 9 | | D00125B | D13 | | | 001-099 |
| 0428 | 24 | | GK | | 4-0 | 23-12-11 | D41531J | | 9 | | D00125B | D13 | | | 115-199 |
| 0429 | 24 | | GK | | 2-9 | 31-51-33 | D41453J | | 23 | | D00005A | A13 | | | 001-099 |
| 0429 | 24 | | GK | | 4-0 | 31-51-33 | D41453J | | 23 | | D00005A | A13 | | | 115-199 |
| 0430 | 22 | | GA | | 2-3 | 23-12-21 | D00129B | | D03 | | GD01758 | DC.. | 2 | | 001-099 |
| 0430 | 22 | | GA | | 4-0 | 23-12-21 | D00129B | | D03 | | GD01758 | DC.. | 2 | | 115-199 |
| 0431 | 24 | | GK | | 2-5 | 23-12-21 | D41533J | | 5 | | D00129B | A03 | | | 001-099 |
| 0431 | 24 | | GK | | 4-0 | 23-12-21 | D41533J | | 5 | | D00129B | A03 | | | 115-199 |
| 0432 | 24 | | GK | | 2-5 | 23-12-21 | D41533J | | 6 | | D00129B | B03 | | | 001-099 |
| 0432 | 24 | | GK | | 4-0 | 23-12-21 | D41533J | | 6 | | D00129B | B03 | | | 115-199 |
| 0433 | 24 | | GK | | 2-5 | 23-12-21 | D41533J | | 1 | | D00129B | C03 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 20

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | |
| 0433 | 24 | GK | | | 4-0 | 23-12-21 | D41533J | 1 | | | D00129B | C03 | | | 115-199 |
| 0434 | 20 | GA | | | 1-6 | 23-12-21 | D41533J | | | AP | GD01759 | ST.. | 2 | | 001-099 |
| 0434 | 20 | GA | | | 1-6 | 23-12-21 | D41533J | | | AP | GD01757 | ST.. | 2 | | 115-199 |
| 0435 | 24 | GK | | | 2-8 | 31-31-61 | D41319J | 4 | | | D00299B | E02 | | | 001-099 |
| 0442 | 24 | GK | | | 3-0 | 23-21-11 | D00135B | B04 | | | D41453J | 36 | | | 001-099 |
| 0442 | 24 | GK | | | 3-0 | 23-21-11 | D41453J | 36 | | | D00135B | B04 | | | 115-199 |
| 0445 | 24 | GK | | | 4-0 | 23-41-11 | D41371J | 32 | | | GD01759 | ST.. | 2 | | 115-199 |
| 0446 | 24 | GK | | | 4-0 | 23-41-11 | D41371J | 29 | | | GD01759 | ST.. | 2 | | 115-199 |
| 0447 | 24 | GK | | | 4-0 | 23-41-11 | D41371J | 24 | | | GD01760 | ST.. | 2 | | 115-199 |
| 0448 | 20 | GA | | | 3-8 | 23-51-14 | D41371J | 46 | | | GD01760 | ST.. | 2 | | 001-099 |
| 0448 | 20 | GA | | | 6-0 | 23-51-14 | D41687J | 15 | | | GD01760 | ST.. | 2 | | 115-199 |
| 0449 | 20 | GA | | | 3-8 | 23-51-14 | D41371J | 49 | | | GD01760 | ST.. | 2 | | 001-099 |
| 0449 | 20 | GA | | | 6-0 | 23-51-14 | D41687J | 18 | | | GD01760 | ST.. | 2 | | 115-199 |
| 0450 | 20 | GA | | | 4-0 | 23-51-14 | D41689J | 18 | | | GD01760 | ST.. | 2 | | 115-199 |
| 0451 | 20 | GA | | | 4-0 | 23-51-14 | D41689J | 15 | | | GD01760 | ST.. | 2 | | 115-199 |
| 0452 | 24 | GK | | | 3-8 | 31-51-33 | D41541J | 41 | | | D41453J | 42 | | | 001-099 |
| 0452 | 24 | GK | | | 4-0 | 31-51-33 | D41541J | 41 | | | D41453J | 42 | | | 115-199 |
| 0453 | 20 | GA | | | 3-8 | 23-51-14 | D41371J | 43 | | | GD01760 | DC.. | 2 | | 001-099 |
| 0453 | 20 | GA | | | 6-0 | 23-51-14 | D41687J | 22 | | | GD01760 | DC.. | 2 | | 115-199 |
| 0454 | 22 | GA | | | 3-8 | 23-51-14 | D00299B | B02 | | | GD01760 | DC.. | 2 | | 001-099 |
| 0454 | 20 | GA | | | 4-0 | 23-51-14 | D41689J | 22 | | | GD01760 | DC.. | 2 | | 115-199 |
| 0455 | 20 | GA | | | 1-6 | 23-41-11 | D41541J | | | AT | GD01752 | ST.. | 2 | | ALL |
| 0456 | 22 | GA | | | 2-9 | 23-31-17 | D41453J | 22 | | | D40672J | 6 | | | 001-099 |
| 0456 | 24 | GK | | | 3-0 | 23-31-11 | D00007B | A02 | | | TB0141Y | A037 | BJ | | 115-199 |
| 0457 | 24 | GK | | | 3-0 | 23-31-11 | D00005B | A09 | | | TB0141Y | A037 | BJ | | 115-199 |
| 0458 | 24 | GK | | | 2-5 | 23-12-21 | D41533J | 8 | | | D00129B | C13 | | | 001-099 |
| 0459 | 24 | GK | | | 2-5 | 23-12-21 | D41533J | 9 | | | D00129B | D13 | | | 001-099 |
| 0459 | 24 | GK | | | 3-0 | 23-31-13 | D41453J | 20 | | | TB0141Y | A043 | BJ | | 115-199 |
| 0460 | 20 | GA | | | 3-0 | 23-42-11 | D41551J | | | AU | GD01760 | ST.. | 2 | | 115-199 |
| 0461 | 16 | GA | | | 3-8 | 23-12-11 | D40734J | 4 | | | SM00013 | | WI | | 001-099 |
| 0461 | 22 | GA | | | 3-0 | 23-42-11 | D00005A | D01 | | | TB0141Y | C043 | BJ | | 115-199 |
| 0462 | 16 | GA | | | 4-11 | 23-12-11 | D00125C | 2 | | | SM00013 | | WI | | 001-099 |
| 0463 | 16 | GA | | | 4-8 | 23-12-11 | D41531J | 7 | | | SM00013 | | WI | | 001-099 |
| 0463 | 22 | GA | | | 4-0 | 23-42-12 | D41700J | 8 | | | TB0141Y | C043 | BJ | | 115-199 |
| 0464 | 16 | GA | | | 2-9 | 23-12-11 | D00125C | 4 | | | GD01758 | DC.. | 2 | | 001-099 |
| 0464 | 24 | GK | | | 3-0 | 23-42-12 | D41700J | 5 | | | D00005A | C01 | | | 115-199 |
| 0465 | 16 | GA | | | 4-6 | 23-12-21 | D40672J | 4 | | | SM00012 | | WI | | 001-099 |
| 0465 | 24 | GK | | | 3-0 | 23-42-12 | D41700J | 6 | | | D00005A | C02 | | | 115-199 |
| 0466 | 16 | GA | | | 4-5 | 23-12-21 | D00129C | 2 | | | SM00012 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 21

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 0466 | 24 | | GK | | 3-0 | 23-42-12 | D41700J | 7 | | | D00005A | C03 | | | 115-199 |
| 0467 | 18 | | GA | | 4-6 | 23-12-21 | D41533J | 7 | 18 | | SM00012 | | WI | | 001-099 |
| 0467 | 22 | | GA | | 4-0 | 23-42-12 | D41700J | 9 | | | TB0141Y | C043 | BJ | | 115-199 |
| 0468 | 16 | | GA | | 2-2 | 23-12-21 | D00129C | 4 | | | GD01758 | DC.. | 2 | | 001-099 |
| 0469 | 24 | | GK | | 3-4 | 23-71-11 | D41541J | 44 | | | D41561J | 13 | | | 001-099 |
| 0469 | 22 | | GA | | 4-0 | 23-42-11 | D41700J | 2 | | | TB0141Y | C044 | BJ | | 115-199 |
| 0471 | 24 | | GK | | 4-0 | 23-12-21 | D00129B | C13 | | | D41533J | 8 | | | 115-199 |
| 0472 | 24 | | GK | | 4-0 | 23-12-21 | D00129B | D13 | | | D41533J | 9 | | | 115-199 |
| 0473 | 24 | | GK | | 2-6 | 23-51-11 | D41553J | 12 | | | TB0141Z | 40 | BJ | | 001-099 |
| 0474 | 24 | | GK | | 2-9 | 23-51-11 | D41453J | 8 | | | TB0141Z | 45 | BJ | | 001-099 |
| 0475 | 24 | | GK | | 2-2 | 23-51-11 | D41553J | 23 | | | TB0141Z | 45 | BJ | | 001-099 |
| 0476 | 24 | | GK | | 2-7 | 23-51-11 | D41453J | 5 | | | GD01756 | ST.. | 2 | | 001-099 |
| 0477 | 24 | | GK | | 2-7 | 23-51-11 | D41453J | 9 | | | GD01756 | ST.. | 2 | | 001-099 |
| 0478 | 24 | | GK | | 2-8 | 23-51-21 | D41555J | 12 | | | TB0141Z | 40 | BJ | | 001-099 |
| 0479 | 24 | | GK | | 2-3 | 23-51-21 | D41555J | 13 | | | TB0141Z | 46 | BJ | | 001-099 |
| 0480 | 24 | | GK | | 2-3 | 23-51-21 | D41555J | 23 | | | TB0141Z | 45 | BJ | | 001-099 |
| 0481 | 24 | | GK | | 2-8 | 23-51-41 | D41559J | 12 | | | TB0141Z | 40 | BJ | | 001-099 |
| 0482 | 24 | | GK | | 2-3 | 23-51-41 | D41559J | 13 | | | TB0141Z | 46 | BJ | | 001-099 |
| 0483 | 24 | | GK | | 2-3 | 23-51-41 | D41559J | 23 | | | TB0141Z | 45 | BJ | | 001-099 |
| 0489 | 24 | | GK | | 2-11 | 23-51-14 | TB0141Z | 31 | BJ | | TB0141B | A049 | 2 | | 001-099 |
| 0489 | 24 | | GK | | 3-0 | 23-51-14 | TB0141Z | 31 | BJ | | TB0141B | A049 | 2 | | 115-199 |
| 0490 | 20 | | GA | | 1-4 | 23-51-14 | TB0141B | C049 | 2 | | GD01757 | ST.. | 2 | | 001-099 |
| 0490 | 20 | | GA | | 3-0 | 23-51-14 | TB0141B | C049 | 2 | | GD01757 | ST.. | 2 | | 115-199 |
| 0491 | 24 | | GK | | 2-5 | 23-51-14 | TB0141Z | 68 | BJ | | TB0141B | A051 | 2 | | 001-099 |
| 0491 | 24 | | GK | | 3-0 | 23-51-14 | TB0141Z | 32 | BJ | | TB0141B | A051 | 2 | | 115-199 |
| 0492 | 20 | | GA | | 2-5 | 23-51-14 | TB0141B | C051 | 2 | | GD01760 | ST.. | 2 | | 001-099 |
| 0492 | 20 | | GA | | 4-0 | 23-51-14 | TB0141B | C051 | 2 | | GD01760 | ST.. | 2 | | 115-199 |
| 0496 | 24 | | GK | | 3-4 | 23-51-11 | TB0141Z | 7 | BJ | | D00005B | D10 | | | 001-099 |
| 0497 | 24 | | GK | | 3-2 | 23-51-11 | TB0141Z | 12 | BJ | | D00005B | A07 | | | 001-099 |
| 0503 | 24 | | GK | | 2-9 | 23-51-11 | D41453J | 7 | | | TB0141Z | 46 | BJ | | 001-099 |
| 0504 | 24 | | GK | | 2-2 | 23-51-11 | D41553J | 13 | | | TB0141Z | 46 | BJ | | 001-099 |
| 0505 | 24 | | GK | | 3-2 | 23-51-11 | D41453J | 6 | | | TB0141Z | 40 | BJ | | 001-099 |
| 0515 | 22 | | GA | | 4-6 | 23-34-15 | D41453J | 27 | | | SM00011 | | WI | | 001-099 |
| 0515 | 22 | | GA | | 3-0 | 23-34-15 | D41453J | 27 | | | SM00011 | | WI | | 115-199 |
| 0524 | 24 | | GK | | 3-6 | 23-32-02 | D41513J | 3 | | | TB0141Y | A075 | BJ | | 001-099 |
| 0524 | 24 | | GK | | 3-0 | 23-32-02 | D41513J | 3 | | | TB0141Y | C006 | BJ | | 115-199 |
| 0526 | 24 | | GK | | 2-9 | 23-32-02 | D41513J | 6 | | | TB0141Y | A043 | BJ | | 001-099 |
| 0526 | 24 | | GK | | 3-0 | 23-32-02 | D41513J | 6 | | | TB0141Y | A043 | BJ | | 115-199 |
| 0527 | 24 | | GK | | 2-5 | 23-32-02 | D41513J | 7 | | | TB0141Z | 7 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 22

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | |
| 0527 | 24 | GK | | | 3-0 | 23-32-02 | D41513J | 7 | | | TB0141Z | 7 | BJ | | 115-199 |
| 0528 | 24 | GK | | | 2-5 | 23-32-02 | D41513J | 8 | | | TB0141Z | 5 | BJ | | 001-099 |
| 0528 | 24 | GK | | | 3-0 | 23-32-02 | D41513J | 8 | | | TB0141Y | A006 | BJ | | 115-199 |
| 0536 | 24 | GK | | | 2-6 | 23-31-41 | D00005B | C14 | | | TB0141A | C058 | 2 | | 001-099 |
| 0536 | 24 | GK | | | 3-0 | 23-31-41 | D00005B | C14 | | | TB0141A | C058 | 2 | | 115-199 |
| 0537 | 20 | GA | | | 1-5 | 23-31-41 | TB0141A | A058 | 2 | | GD01757 | DC.. | 2 | | 001-099 |
| 0537 | 20 | GA | | | 3-0 | 23-31-41 | TB0141A | A058 | 2 | | GD01757 | DC.. | 2 | | 115-199 |
| 0538 | 20 | GA | | | 1-5 | 23-31-41 | TB0141A | A056 | 2 | | GD01757 | DC.. | 2 | | 001-099 |
| 0538 | 20 | GA | | | 3-0 | 23-31-41 | TB0141A | A056 | 2 | | GD01757 | DC.. | 2 | | 115-199 |
| 0539 | 24 | GK | | | 2-6 | 23-31-41 | D00005B | C06 | | | TB0141A | C056 | 2 | | 001-099 |
| 0539 | 24 | GK | | | 3-0 | 23-31-41 | D00005B | C06 | | | TB0141A | C056 | 2 | | 115-199 |
| 0540 | 24 | GK | | | 2-6 | 23-31-41 | D00005B | C13 | | | TB0141A | C057 | 2 | | 001-099 |
| 0540 | 24 | GK | | | 3-0 | 23-31-41 | D00005B | C13 | | | TB0141A | C057 | 2 | | 115-199 |
| 0541 | 20 | GA | | | 1-5 | 23-31-41 | TB0141A | A057 | 2 | | GD01757 | DC.. | 2 | | 001-099 |
| 0541 | 20 | GA | | | 3-0 | 23-31-41 | TB0141A | A057 | 2 | | GD01757 | DC.. | 2 | | 115-199 |
| 0542 | 20 | GA | | | 1-5 | 23-31-41 | TB0141A | A059 | 2 | | GD01757 | DC.. | 2 | | 001-099 |
| 0542 | 20 | GA | | | 3-0 | 23-31-41 | TB0141A | A059 | 2 | | GD01757 | DC.. | 2 | | 115-199 |
| 0551 | 20 | GA | | | 3-8 | 23-11-11 | D40686J | 4 | | | D00299C | 2 | | | 001-099 |
| 0552 | 20 | GA | | | 3-8 | 23-11-11 | D40686J | 5 | | | D00299C | 3 | | | 001-099 |
| 0553 | 20 | GA | | | 3-8 | 23-11-11 | D40686J | 6 | | | D00299C | 7 | | | 001-099 |
| 0554 | 20 | GA | | | 2-6 | 23-11-11 | D00299C | 8 | | | GD01751 | AC.. | 2 | | 001-099 |
| 0555 | 20 | GA | | | 2-6 | 23-11-11 | D00299C | 10 | | | GD01751 | ST.. | 2 | | 001-099 |
| 0556 | 20 | GA | | | 4-1 | 23-11-11 | D42031J | | | CP | GD01751 | ST.. | 2 | | 001-099 |
| 0558 | 22 | GA | | | 3-10 | 23-11-11 | D42031J | 5 | | | D00299B | D05 | | | 001-099 |
| 0559 | 22 | GA | | | 3-10 | 23-11-11 | D42031J | 3 | | | D00299B | F05 | | | 001-099 |
| 0560 | 22 | GA | | | 3-10 | 23-11-11 | D42031J | 4 | | | D00299B | E05 | | | 001-099 |
| 0561 | 22 | GA | | | 3-10 | 23-11-11 | D42031J | 6 | | | D00299B | D02 | | | 001-099 |
| 0562 | 22 | GA | | | 2-10 | 23-11-11 | D42031J | 7 | | | D42033J | 7 | | | 001-099 |
| 0563 | 22 | GA | | | 2-10 | 23-11-11 | D42031J | 8 | | | D42033J | 8 | | | 001-099 |
| 0564 | 20 | GA | | | 3-7 | 23-11-11 | D00299C | 1 | | | D42033J | 3 | | | 001-099 |
| 0565 | 20 | GA | | | 3-7 | 23-11-11 | D00299C | 9 | | | D42033J | 6 | | | 001-099 |
| 0566 | 22 | GA | | | 3-8 | 23-11-11 | D00299B | B05 | | | D42033J | 1 | | | 001-099 |
| 0567 | 22 | GA | | | 3-8 | 23-11-11 | D00299B | C05 | | | D42033J | 2 | | | 001-099 |
| 0568 | 22 | GA | | | 3-8 | 23-11-11 | D00299B | H05 | | | D42033J | 4 | | | 001-099 |
| 0569 | 22 | GA | | | 2-6 | 23-11-11 | D00299B | C01 | | | TB0141Z | 3 | BJ | | 001-099 |
| 0570 | 20 | GA | | | 3-9 | 23-11-11 | D42033J | 5 | | | TB0141Z | 3 | BJ | | 001-099 |
| 0571 | 24 | GK | | | 3-6 | 23-31-19 | TB0141Z | 5 | BJ | | D41820J | 12 | | | 001-099 |
| 0572 | 24 | GK | | | 3-6 | 23-31-19 | TB0141Z | 7 | BJ | | D41820J | 5 | | | 001-099 |
| 0573 | 24 | GK | | | 2-8 | 23-31-19 | TB0141Y | A043 | BJ | | D41820J | 4 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 23

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | | |
| 0577 | 24 | GK | | 2-9 | 23-31-13 | TB0141Y | A043 | BJ | | | D41453J | 20 | | | 001-099 | |
| 0596 | 22 | GA | | 2-7 | 23-31-19 | TB0141Z | 35 | BJ | | | D41457J | 1 | | | 001-099 | |
| 0597 | 22 | GA | | 3-10 | 23-31-19 | D41457J | 2 | | | | TB0141Y | A075 | BJ | | 001-099 | |
| 0598 | 22 | GA | | 3-7 | 23-31-19 | D41820J | 3 | | | | D41457J | 5 | | | 001-099 | |
| 0771 | 22 | GA | | 3-10 | 23-31-19 | D41457J | 8 | | | | TB0141Y | C075 | BJ | | 001-099 | |
| 1001 | 22 | GT | BI | 3-5 | 23-42-11 | D41541J | 34 | | | | D00005A | B12 | | | 001-099 | |
| 1001 | 22 | GT | BI | 3-0 | 23-42-11 | D41541J | 34 | | | | D00005A | B12 | | | 115-199 | |
| 1001Z | | | BI | 0-0 | 23-42-11 | D41541J | 35 | | | | D00005A | B13 | | | ALL | |
| 1002 | 16 | GT | BQ | 3-0 | 23-12-11 | D00125C | 2 | | | | SM00013 | | WI | | 115-199 | |
| 1002Z | | | BQ | 0-0 | 23-12-11 | D00125C | DED | | | | SM00013 | DED | | | 115-199 | |
| 1003 | 16 | GT | BR | 3-0 | 23-12-11 | D00125C | 4 | | | | GD01758 | DC.. | 2 | | 115-199 | |
| 1003Z | | | BR | 0-0 | 23-12-11 | D00125C | DED | | | | GD01758 | DED | | | 115-199 | |
| 1004 | 16 | GT | BS | 3-0 | 23-12-11 | D41531J | 7 | | | | SM00013 | | WI | | 115-199 | |
| 1004Z | | | BS | 0-0 | 23-12-11 | D41531J | DED | | | | SM00013 | DED | | | 115-199 | |
| 1005 | 16 | GT | BT | 3-0 | 23-12-11 | D40734J | 4 | | | | SM00013 | | WI | | 115-199 | |
| 1005Z | | | BT | 0-0 | 23-12-11 | D40734J | DED | | | | SM00013 | DED | | | 115-199 | |
| 1006 | 16 | GT | BX | 3-0 | 23-12-21 | D00129C | 2 | | | | SM00012 | | WI | | 115-199 | |
| 1006Z | | | BX | 0-0 | 23-12-21 | D00129C | DED | | | | SM00012 | DED | | | 115-199 | |
| 1007 | 16 | GT | BY | 3-0 | 23-12-21 | D00129C | 4 | | | | GD01758 | DC.. | 2 | | 115-199 | |
| 1007Z | | | BY | 0-0 | 23-12-21 | D00129C | DED | | | | GD01758 | DED | | | 115-199 | |
| 1008 | 18 | GT | BZ | 3-0 | 23-12-21 | D41533J | 7 | | | | SM00012 | | WI | | 115-199 | |
| 1008Z | | | BZ | 0-0 | 23-12-21 | D41533J | DED | | | | SM00012 | DED | | | 115-199 | |
| 1009 | 16 | GT | CA | 3-0 | 23-12-21 | D40672J | 4 | | | | SM00012 | | WI | | 115-199 | |
| 1009Z | | | CA | 0-0 | 23-12-21 | D40672J | DED | | | | SM00012 | DED | | | 115-199 | |
| 2001B | 24 | GL | AA | 4-0 | 23-21-11 | D00125B | B13 | | | | TB0141Y | C036 | BJ | | 115-199 | |
| 2001R | 24 | GL | AA | 0-0 | 23-21-11 | D00125B | A13 | | | | TB0141Y | A036 | BJ | | 115-199 | |
| 2002B | 24 | GL | AB | 3-10 | 23-21-11 | D41371J | 12 | | | | D00135B | C08 | | | 001-099 | |
| 2002B | 24 | GL | AB | 3-0 | 23-21-11 | D00135B | B06 | | | | D41689J | 1 | | | 115-199 | |
| 2002R | 24 | GL | AB | 0-0 | 23-21-11 | D41371J | 11 | | | | D00135B | B08 | | | 001-099 | |
| 2002R | 24 | GL | AB | 0-0 | 23-21-11 | D00135B | A06 | | | | D41689J | 2 | | | 115-199 | |
| 2003B | 24 | GL | DH | 3-0 | 23-21-11 | D00135B | C08 | | | | D41687J | 2 | | | 115-199 | |
| 2003R | 24 | GL | DH | 0-0 | 23-21-11 | D00135B | B08 | | | | D41687J | 1 | | | 115-199 | |
| 2008B | 24 | GL | AW | 2-3 | 23-21-11 | D00135B | C02 | | | | TB0141X | B070 | BJ | | 001-099 | |
| 2008B | 24 | GL | AW | 4-0 | 23-21-11 | D00135B | C02 | | | | TB0141Y | C036 | BJ | | 115-199 | |
| 2008R | 24 | GL | AW | 0-0 | 23-21-11 | D00135B | B02 | | | | TB0141X | A070 | BJ | | 001-099 | |
| 2008R | 24 | GL | AW | 0-0 | 23-21-11 | D00135B | B02 | | | | TB0141Y | A036 | BJ | | 115-199 | |
| 2009B | 24 | GL | AL | 2-7 | 23-21-11 | D00125B | B13 | | | | TB0141X | B070 | BJ | | 001-099 | |
| 2009R | 24 | GL | AL | 0-0 | 23-21-11 | D00125B | A13 | | | | TB0141X | A070 | BJ | | 001-099 | |
| 2011B | 22 | GB | AZ | 4-0 | 23-34-16 | D41453J | 18 | | | | D00007B | B05 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 24

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------|-------------|------------------------|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1163 | 286N1163 | E4-3 SHELF (continued) | | | | | | | | | | | | | |
| 2011R | 22 | GB | AZ | | 0-0 | 23-34-16 | D41453J | 17 | | | D00007B | A05 | | | 115-199 |
| 2012B | 22 | GB | BA | | 3-11 | 23-31-21 | D00007B | B15 | | | SM00010 | | WI | | 001-099 |
| 2012B | 22 | GB | BA | | 3-0 | 23-31-21 | D00007B | B15 | | | SM00010 | | WI | | 115-199 |
| 2012R | 22 | GB | BA | | 0-0 | 23-31-21 | D00007B | A15 | | | SM00011 | | WI | | ALL |
| 2013B | 22 | GB | BB | | 4-6 | 23-31-21 | D41453J | 30 | | | SM00010 | | WI | | 001-099 |
| 2013B | 22 | GB | BB | | 3-0 | 23-31-21 | D41453J | 30 | | | SM00010 | | WI | | 115-199 |
| 2013R | 22 | GB | BB | | 0-0 | 23-31-21 | D41453J | 29 | | | SM00011 | | WI | | ALL |
| 2014B | 22 | GB | BC | | 4-6 | 23-31-21 | D41453J | 32 | | | SM00010 | | WI | | 001-099 |
| 2014B | 22 | GB | BC | | 3-0 | 23-31-21 | D41453J | 32 | | | SM00010 | | WI | | 115-199 |
| 2014R | 22 | GB | BC | | 0-0 | 23-31-21 | D41453J | 31 | | | SM00011 | | WI | | ALL |
| 2015B | 22 | GB | B6 | | 2-6 | 23-31-19 | D41513J | 2 | | | D41457J | 10 | | | 001-099 |
| 2015B | 22 | GB | CM | | 4-0 | 23-32-02 | D41513J | 2 | | | D00007B | B04 | | | 115-199 |
| 2015R | 22 | GB | B6 | | 0-0 | 23-31-19 | D41513J | 1 | | | D41457J | 9 | | | 001-099 |
| 2015R | 22 | GB | CM | | 0-0 | 23-32-02 | D41513J | 1 | | | D00007B | A04 | | | 115-199 |
| 2016B | 24 | GL | CN | | 4-0 | 23-51-15 | D41220J | 2 | | | GD01750 | ST.. | 2 | | 115-199 |
| 2016R | 24 | GL | CN | | 0-0 | 23-51-15 | D41220J | 1 | | | TB0141Z | 7 | BJ | | 115-199 |
| 2018B | 24 | GL | BY | | 3-0 | 23-21-11 | D41453J | 4 | | | D00135B | B05 | | | 001-099 |
| 2018R | 24 | GL | BY | | 0-0 | 23-21-11 | D41453J | 3 | | | D00135B | A05 | | | 001-099 |
| 2021B | 24 | GL | AM | | 2-5 | 23-21-11 | D00129B | B13 | | | TB0141X | C071 | BJ | | 001-099 |
| 2021R | 24 | GL | AM | | 0-0 | 23-21-11 | D00129B | A13 | | | TB0141X | A071 | BJ | | 001-099 |
| 2022B | 24 | GL | DE | | 2-3 | 23-21-11 | D00135B | B03 | | | TB0141X | C071 | BJ | | 001-099 |
| 2022R | 24 | GL | DE | | 0-0 | 23-21-11 | D00135B | A03 | | | TB0141X | A071 | BJ | | 001-099 |
| 2023B | 24 | GL | DF | | 2-10 | 23-31-19 | D41820J | 2 | | * | D00007B | B05 | | | 001-099 |
| 2023R | 24 | GL | DF | | 0-0 | 23-31-19 | D41820J | 7 | | | D00007B | A05 | | | 001-099 |
| 2024B | 22 | GB | CQ | | 3-7 | 23-32-02 | D41513J | 5 | | | SM00010 | | WI | | 001-099 |
| 2024R | 22 | GB | CQ | | 0-0 | 23-32-02 | D41513J | 4 | | | SM00011 | | WI | | 001-099 |
| 2025B | 24 | GL | EA | | 3-9 | 23-21-11 | D00299B | D03 | | | D00135B | B06 | | | 001-099 |
| 2025B | 22 | GB | EA | | 2-0 | 23-32-02 | D41513J | 5 | | | SM00010 | | WI | | 115-199 |
| 2025R | 24 | GL | EA | | 0-0 | 23-21-11 | D00299B | C03 | | | D00135B | A06 | | | 001-099 |
| 2025R | 22 | GB | EA | | 0-0 | 23-32-02 | D41513J | 4 | | | SM00011 | | WI | | 115-199 |
| 2028B | 24 | GL | B3 | | 3-8 | 23-51-14 | D00299B | E01 | | | GD01757 | ST.. | 2 | | 001-008 |
| 2028B | 24 | GL | B3 | | 3-8 | 23-51-14 | D00299B | E01 | | | GD01759 | ST.. | 2 | | 009-099 |
| 2028R | 24 | GL | B3 | | 0-0 | 23-51-14 | D00299B | D01 | | | TB0141Z | 68 | BJ | | 001-099 |
| 2029B | 24 | GL | B4 | | 3-8 | 23-51-14 | D00299B | B01 | | | GD01757 | ST.. | 2 | | 001-008 |
| 2029B | 24 | GL | B4 | | 3-8 | 23-51-14 | D00299B | B01 | | | GD01759 | ST.. | 2 | | 009-099 |
| 2029R | 24 | GL | B4 | | 0-0 | 23-51-14 | D00299B | A01 | | | TB0141Z | 69 | BJ | | 001-099 |
| 2030B | 24 | GL | DG | | 3-2 | 23-31-19 | D41457J | 6 | | | D00007B | B04 | | | 001-099 |
| 2030R | 24 | GL | DG | | 0-0 | 23-31-19 | D41457J | 7 | | | D00007B | A04 | | | 001-099 |
| 2031B | 24 | GL | B5 | | 3-7 | 23-31-19 | D41820J | 2 | | * | D41457J | 4 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 25

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | 286N1163 | | | E4-3 SHELF (continued) | | | | | | | | | | | |
| 2031R | 24 | GL | B5 | | 0-0 | 23-31-19 | D41820J | | 6 | | D41457J | | 3 | | 001-099 |
| 2502B | 24 | G2 | BD | | 2-6 | 23-41-11 | D00005A | | B11 | | TB0141Z | | 42 | BJ | 001-099 |
| 2502B | 24 | G2 | BD | | 3-0 | 23-41-11 | D00005A | | B11 | | TB0141Z | | 42 | BJ | 115-199 |
| 2502R | 24 | G2 | BD | | 0-0 | 23-41-11 | D00005A | | B10 | | TB0141Z | | 41 | BJ | ALL |
| 2502Z | | | BD | | 0-0 | 23-41-11 | D00005A | | DED | | GD01754 | ST.. | 2 | | ALL |
| 2503B | 24 | G2 | BE | | 2-10 | 23-41-11 | D41371J | | 19 | | TB0141Z | | 42 | BJ | 001-099 |
| 2503B | 24 | G2 | BE | | 4-0 | 23-41-11 | D41371J | | 19 | | TB0141Z | | 42 | BJ | 115-199 |
| 2503R | 24 | G2 | BE | | 0-0 | 23-41-11 | D41371J | | 18 | | TB0141Z | | 41 | BJ | ALL |
| 2503Z | | | BE | | 0-0 | 23-41-11 | D41371J | | 21 | | GD01754 | ST.. | 2 | | ALL |
| 2504B | 24 | G2 | BF | | 3-5 | 23-41-11 | D41541J | | 23 | | D00005A | | B09 | | 001-099 |
| 2504B | 24 | G2 | BF | | 3-0 | 23-41-11 | D41541J | | 23 | | D00005A | | B09 | | 115-199 |
| 2504R | 24 | G2 | BF | | 0-0 | 23-41-11 | D41541J | | 24 | | D00005A | | B08 | | ALL |
| 2504Z | | | BF | | 0-0 | 23-41-11 | D41541J | | | AT | D00005A | DED | | | ALL |
| 2505B | 24 | G2 | BG | | 2-8 | 23-41-11 | D41648J | | 1 | | TB0141Z | | 42 | BJ | 001-099 |
| 2505B | 24 | G2 | BG | | 4-0 | 23-41-11 | D41648J | | 1 | | TB0141Z | | 42 | BJ | 115-199 |
| 2505R | 24 | G2 | BG | | 0-0 | 23-41-11 | D41648J | | 2 | | TB0141Z | | 41 | BJ | ALL |
| 2505Z | | | BG | | 0-0 | 23-41-11 | D41648J | | 4 | | GD01754 | ST.. | 2 | | ALL |
| 2507B | 24 | G2 | BN | | 3-4 | 23-71-11 | D41561J | | 20 | | D41541J | | 31 | | 001-099 |
| 2507B | 24 | G2 | BN | | 4-0 | 23-71-11 | D41561J | | 20 | | D41541J | | 31 | | 115-199 |
| 2507R | 24 | G2 | BN | | 0-0 | 23-71-11 | D41561J | | 9 | | D41541J | | 32 | | ALL |
| 2507Z | | | BN | | 0-0 | 23-71-11 | D41561J | | | AN | D41541J | | | AM | ALL |
| 2508B | 24 | G2 | BO | | 3-4 | 23-71-11 | D41561J | | 10 | | D41541J | | 29 | | 001-099 |
| 2508B | 24 | G2 | BO | | 4-0 | 23-71-11 | D41561J | | 10 | | D41541J | | 29 | | 115-199 |
| 2508R | 24 | G2 | BO | | 0-0 | 23-71-11 | D41561J | | 21 | | D41541J | | 28 | | ALL |
| 2508Z | | | BO | | 0-0 | 23-71-11 | D41561J | | | AN | D41541J | | | AM | ALL |
| 2510B | 24 | G2 | CI | | 2-10 | 23-41-11 | D41371J | | 30 | | TB0141Z | | 42 | BJ | 001-099 |
| 2510B | 24 | G2 | CI | | 4-0 | 23-41-11 | D41371J | | 30 | | TB0141Z | | 42 | BJ | 115-199 |
| 2510R | 24 | G2 | CI | | 0-0 | 23-41-11 | D41371J | | 31 | | TB0141Z | | 41 | BJ | ALL |
| 2510Z | | | CI | | 0-0 | 23-41-11 | D41371J | | 33 | | GD01754 | ST.. | 2 | | ALL |
| 2511B | 24 | G2 | CJ | | 2-10 | 23-41-11 | D41371J | | 26 | | TB0141Z | | 42 | BJ | 001-099 |
| 2511B | 24 | G2 | CJ | | 4-0 | 23-41-11 | D41371J | | 26 | | TB0141Z | | 42 | BJ | 115-199 |
| 2511R | 24 | G2 | CJ | | 0-0 | 23-41-11 | D41371J | | 27 | | TB0141Z | | 41 | BJ | ALL |
| 2511Z | | | CJ | | 0-0 | 23-41-11 | D41371J | | 28 | | GD01754 | ST.. | 2 | | ALL |
| 2512B | 24 | G2 | CK | | 2-10 | 23-41-11 | D41371J | | 23 | | TB0141Z | | 42 | BJ | 001-099 |
| 2512B | 24 | G2 | CK | | 4-0 | 23-41-11 | D41371J | | 23 | | TB0141Z | | 42 | BJ | 115-199 |
| 2512R | 24 | G2 | CK | | 0-0 | 23-41-11 | D41371J | | 22 | | TB0141Z | | 41 | BJ | ALL |
| 2512Z | | | CK | | 0-0 | 23-41-11 | D41371J | | 25 | | GD01754 | ST.. | 2 | | ALL |
| 2513B | 24 | G2 | CP | | 4-0 | 23-51-15 | D41220J | | 4 | | GD01751 | ST.. | 2 | | 115-199 |
| 2513R | 24 | G2 | CP | | 0-0 | 23-51-15 | D41220J | | 3 | | TB0141Z | | 12 | BJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 26

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1163 | | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | |
| 2513Z | | | | CP | 0-0 | 23-51-15 | D41220J | | | AV | TB0141Z | DED | | | 115-199 |
| 2514B | 24 | G2 | | CM | 3-4 | 23-71-11 | D41541J | 46 | | | D41561J | 25 | | | 001-099 |
| 2514R | 24 | G2 | | CM | 0-0 | 23-71-11 | D41541J | 45 | | | D41561J | 24 | | | 001-099 |
| 2514Z | | | | CM | 0-0 | 23-71-11 | D41541J | | | AM | D41561J | | | AN | 001-099 |
| 2526B | 24 | G2 | | CP | 3-10 | 23-11-11 | D42031J | 10 | | | D00299B | H03 | | | 001-099 |
| 2526R | 24 | G2 | | CP | 0-0 | 23-11-11 | D42031J | 9 | | | D00299B | G03 | | | 001-099 |
| 2526Z | | | | CP | 0-0 | 23-11-11 | D42031J | | | CP | D00299B | DED | | | 001-099 |
| 4251B | 24 | G4 | | BJ | 2-10 | 23-42-11 | D41551J | 2 | | | D00005A | A10 | | | 001-099 |
| 4251B | 24 | G4 | | BJ | 4-0 | 23-42-11 | D41551J | 2 | | | D00005A | A10 | | | 115-199 |
| 4251G | 24 | G4 | | BJ | 0-0 | 23-42-11 | D41551J | 4 | | | D00005A | A12 | | | ALL |
| 4251R | 24 | G4 | | BJ | 0-0 | 23-42-11 | D41551J | 1 | | | D00005A | A09 | | | ALL |
| 4251Y | 24 | G4 | | BJ | 0-0 | 23-42-11 | D41551J | 3 | | | D00005A | A11 | | | ALL |
| 4251Z | | | | BJ | 0-0 | 23-42-11 | D41551J | | | AI | D00005A | DED | | | ALL |
| 4252B | 24 | G4 | | BM | 2-10 | 23-42-11 | D41551J | 7 | | | D00005A | A06 | | | 001-099 |
| 4252B | 24 | G4 | | BM | 4-0 | 23-42-11 | D41551J | 7 | | | D00005A | A06 | | | 115-199 |
| 4252G | 24 | G4 | | BM | 0-0 | 23-42-11 | D41551J | 18 | | | D00005A | A08 | | | ALL |
| 4252R | 24 | G4 | | BM | 0-0 | 23-42-11 | D41551J | 6 | | | D00005A | A05 | | | ALL |
| 4252Y | 24 | G4 | | BM | 0-0 | 23-42-11 | D41551J | 17 | | | D00005A | A07 | | | ALL |
| 4252Z | | | | BM | 0-0 | 23-42-11 | D41551J | | | AJ | D00005A | DED | | | ALL |
| 4253B | 24 | G4 | | BK | 4-0 | 23-42-11 | D41551J | 12 | | | D00005A | D09 | | | 115-199 |
| 4253G | 24 | G4 | | BK | 0-0 | 23-42-11 | D41551J | 25 | | | D00005A | D11 | | | 115-199 |
| 4253R | 24 | G4 | | BK | 0-0 | 23-42-11 | D41551J | 11 | | | D00005A | D08 | | | 115-199 |
| 4253Y | 24 | G4 | | BK | 0-0 | 23-42-11 | D41551J | 24 | | | D00005A | D10 | | | 115-199 |
| 4253Z | | | | BK | 0-0 | 23-42-11 | D41551J | | | AK | D00005A | DED | | | 115-199 |
| 4254B | 24 | G4 | | BL | 2-10 | 23-42-11 | D41551J | 15 | | | D00005A | A02 | | | 001-099 |
| 4254B | 24 | G4 | | BL | 4-0 | 23-42-11 | D41551J | 15 | | | D00005A | A02 | | | 115-199 |
| 4254G | 24 | G4 | | BL | 0-0 | 23-42-11 | D41551J | 27 | | | D00005A | A04 | | | ALL |
| 4254R | 24 | G4 | | BL | 0-0 | 23-42-11 | D41551J | 14 | | | D00005A | A01 | | | ALL |
| 4254Y | 24 | G4 | | BL | 0-0 | 23-42-11 | D41551J | 26 | | | D00005A | A03 | | | ALL |
| 4254Z | | | | BL | 0-0 | 23-42-11 | D41551J | | | AL | D00005A | DED | | | ALL |
| 4255B | 24 | G4 | | XX | 2-10 | 23-42-11 | D41551J | 12 | | | D00005A | A15 | | | 001-099 |
| 4255B | 24 | G4 | | CL | 4-0 | 23-42-11 | D41551J | 30 | | | D00005A | CAP | Y | | 115-199 |
| 4255G | 24 | G4 | | XX | 0-0 | 23-42-11 | D41551J | 25 | | | D00005A | B15 | | | 001-099 |
| 4255G | 24 | G4 | | CL | 0-0 | 23-42-11 | D41551J | 22 | | | D00005A | CAP | Y | | 115-199 |
| 4255R | 24 | G4 | | XX | 0-0 | 23-42-11 | D41551J | 11 | | | D00005A | A14 | | | 001-099 |
| 4255R | 24 | G4 | | CL | 0-0 | 23-42-11 | D41551J | 29 | | | D00005A | CAP | Y | | 115-199 |
| 4255Y | 24 | G4 | | XX | 0-0 | 23-42-11 | D41551J | 24 | | | D00005A | B14 | | | 001-099 |
| 4255Y | 24 | G4 | | CL | 0-0 | 23-42-11 | D41551J | 31 | | | D00005A | CAP | Y | | 115-199 |
| 4255Z | | | | XX | 0-0 | 23-42-11 | D41551J | | | XX | D00005A | DED | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 27

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1163 | 286N1163 | | | | E4-3 SHELF (continued) | | | | | | | | | | | | |
| 4255Z | | | | CL | 0-0 | 23-42-11 | D41551J | | | | AU | D00005A | DED | | 115-199 | | |
| 5001B | 24 | G2 | | AD | 4-0 | 23-21-11 | D00135B | B03 | | | | TB0141Y | C005 | BJ | 115-199 | | |
| 5001R | 24 | G2 | | AD | 0-0 | 23-21-11 | D00135B | A03 | | | | TB0141Y | A005 | BJ | 115-199 | | |
| 5001Z | | | | AD | 0-0 | 23-21-11 | D00135B | DED | | | | GD01750 | ST.. | 2 | 115-199 | | |
| 5002B | 24 | G2 | | AE | 4-0 | 23-21-11 | D00129B | B13 | | | | TB0141Y | C005 | BJ | 115-199 | | |
| 5002R | 24 | G2 | | AE | 0-0 | 23-21-11 | D00129B | A13 | | | | TB0141Y | A005 | BJ | 115-199 | | |
| 5002Z | | | | AE | 0-0 | 23-21-11 | D00129B | DED | | | | GD01750 | ST.. | 2 | 115-199 | | |
| 5016B | 24 | G2 | | BP | 2-4 | 23-12-11 | D41531J | 12 | | | | D00125B | B07 | | 001-099 | | |
| 5016B | 24 | G2 | | BP | 4-0 | 23-12-11 | D41531J | 12 | | | | D00125B | B07 | | 115-199 | | |
| 5016R | 24 | G2 | | BP | 0-0 | 23-12-11 | D41531J | 11 | | | | D00125B | A07 | | ALL | | |
| 5016Z | | | | BP | 0-0 | 23-12-11 | D41531J | | | | AO | D00125B | DED | | ALL | | |
| 5017B | 24 | G2 | | BW | 2-5 | 23-12-21 | D41533J | 12 | | | | D00129B | B07 | | 001-099 | | |
| 5017B | 24 | G2 | | BW | 4-0 | 23-12-21 | D41533J | 12 | | | | D00129B | B07 | | 115-199 | | |
| 5017R | 24 | G2 | | BW | 0-0 | 23-12-21 | D41533J | 11 | | | | D00129B | A07 | | ALL | | |
| 5017Z | | | | BW | 0-0 | 23-12-21 | D41533J | | | | AP | D00129B | DED | | ALL | | |
| 5021B | 24 | G2 | | CG | 3-0 | SPARE | D41689J | 19 | | | | D41319J | 16 | | 115-199 | | |
| 5021R | 24 | G2 | | CG | 0-0 | SPARE | D41689J | 20 | | | | D41319J | 17 | | 115-199 | | |
| 5021Z | | | | CG | 0-0 | SPARE | D41689J | 21 | | | | D41319J | 18 | | 115-199 | | |
| FRAI | | | | | 0-0 | 23-42-11 | D41551J | | | | AI | D41551J | 5 | | 001-099 | | |
| FRAI | | | | | 1-0 | 23-42-11 | D41551J | | | | AI | D41551J | 5 | | 115-199 | | |
| FRAJ | | | | | 0-0 | 23-42-11 | D41551J | | | | AJ | D41551J | 16 | | 001-099 | | |
| FRAJ | | | | | 1-0 | 23-42-11 | D41551J | | | | AJ | D41551J | 16 | | 115-199 | | |
| FRAK | | | | | 1-0 | 23-42-11 | D41551J | | | | AK | D41551J | 13 | | 115-199 | | |
| FRAL | | | | | 0-0 | 23-42-11 | D41551J | | | | AL | D41551J | 28 | | 001-099 | | |
| FRAL | | | | | 1-0 | 23-42-11 | D41551J | | | | AL | D41551J | 28 | | 115-199 | | |
| FRAM | | | | | 0-0 | 23-71-11 | D41541J | | | | AM | D41541J | 40 | | 001-099 | | |
| FRAM | | | | | 1-0 | 23-71-11 | D41541J | | | | AM | D41541J | 40 | | 115-199 | | |
| FRAN | | | | | 0-0 | 23-71-11 | D41561J | | | | AN | D41561J | 22 | | 001-099 | | |
| FRAN | | | | | 1-0 | 23-71-11 | D41561J | | | | AN | D41561J | 22 | | 115-199 | | |
| FRAO | | | | | 0-0 | 23-12-11 | D41531J | | | | AO | D41531J | 3 | | 001-099 | | |
| FRAO | | | | | 1-0 | 23-12-11 | D41531J | | | | AO | D41531J | 3 | | 115-199 | | |
| FRAP | | | | | 0-0 | 23-12-21 | D41533J | | | | AP | D41533J | 3 | | 001-099 | | |
| FRAP | | | | | 1-0 | 23-12-21 | D41533J | | | | AP | D41533J | 3 | | 115-199 | | |
| FRAT | | | | | 0-0 | 23-41-11 | D41541J | | | | AT | D41541J | 25 | | 001-099 | | |
| FRAT | | | | | 1-0 | 23-41-11 | D41541J | | | | AT | D41541J | 25 | | 115-199 | | |
| FRAU | | | | | 1-0 | 23-42-11 | D41551J | | | | AU | D41551J | 23 | | 115-199 | | |
| FRAV | | | | | 0-0 | 23-51-15 | D41220J | | | | AV | D41220J | 5 | | 115-199 | | |
| FRAW | | | | | 0-0 | 23-11-11 | D42031J | | | | CP | D42031J | 11 | | 001-099 | | |
| FRXX | | | | | 0-0 | 23-42-11 | D41551J | | | | XX | D41551J | 13 | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 28

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | | |
|------------|-------------|----|-------|-------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF | | | | | | | | | | | | |
| 0001 | 22 | GA | | | 1-11 | 27-61-14 | D00671A | A05 | | | | D00665A | E11 | | | ALL |
| 0002 | 22 | GA | | | 1-11 | 27-61-14 | D00671A | H01 | | | | D00665A | G03 | | | ALL |
| 0003 | 22 | GA | | | 1-11 | 27-61-14 | D00671A | C07 | | | | D00665A | G05 | | | ALL |
| 0006 | 22 | GA | | | 3-9 | 27-61-14 | D00673A | C07 | | | | D00665A | F05 | | | ALL |
| 0007 | 22 | GA | | | 3-9 | 27-61-14 | D00673A | H01 | | | | D00665A | F03 | | | ALL |
| 0008 | 22 | GA | | | 3-9 | 27-61-14 | D00673A | A05 | | | | D00665A | E12 | | | ALL |
| 0009 | 22 | GA | | | 2-9 | 27-61-14 | TB0108Z | 10 | BJ | | | D00665A | K15 | | | ALL |
| 0011 | 22 | GA | | | 2-6 | 27-61-15 | D00671A | C08 | | | | D00667B | G06 | | | ALL |
| 0012 | 22 | GA | | | 2-6 | 27-61-15 | D00671A | H02 | | | | D00667B | G04 | | | ALL |
| 0013 | 22 | GA | | | 4-1 | 27-61-15 | D00671A | C03 | | | | D00673A | A03 | | | ALL |
| 0014 | 22 | GA | | | 4-10 | 27-61-15 | D00673A | C01 | | | | TB0108Z | 6 | BJ | | ALL |
| 0015 | 22 | GA | | | 3-2 | 27-61-15 | D00673A | H02 | | | | D00667B | F04 | | | ALL |
| 0016 | 22 | GA | | | 3-2 | 27-61-15 | D00673A | C08 | | | | D00667B | F06 | | | ALL |
| 0018 | 22 | GA | | | 3-3 | 27-61-15 | TB0108Z | 10 | BJ | | | D00667A | K15 | | | ALL |
| 0019 | 22 | GA | | | 3-9 | 27-61-16 | D00671A | B07 | | | | D00669B | G14 | | | ALL |
| 0020 | 22 | GA | | | 3-9 | 27-61-16 | D00671A | H03 | | | | D00669B | G12 | | | ALL |
| 0022 | 22 | GA | | | 1-11 | 27-61-16 | D00673A | B07 | | | | D00669B | F14 | | | ALL |
| 0023 | 22 | GA | | | 1-11 | 27-61-16 | D00673A | H03 | | | | D00669B | F12 | | | ALL |
| 0025 | 22 | GA | | | 4-6 | 27-61-16 | TB0108Z | 10 | BJ | | | D00669A | K15 | | | ALL |
| 0026 | 22 | GA | | | 3-8 | 27-31-22 | D00675B | A01 | | | | TB0108Y | A001 | BJ | | ALL |
| 0027 | 22 | GA | | | 3-8 | 27-31-22 | D00675B | B01 | | | | TB0108Y | A001 | BJ | | ALL |
| 0028 | 20 | GA | | | 2-5 | 27-31-22 | D40682J | 4 | | | | TB0108Y | A001 | BJ | | 001-099 |
| 0028 | 20 | GA | | | 3-3 | 27-31-22 | D40682J | 4 | | | | TB0108Y | A001 | BJ | | 115-199 |
| 0029 | 20 | GA | | | 3-8 | 27-31-22 | TB0108Y | A001 | BJ | | | D41773J | 21 | | | ALL |
| 0030 | 22 | GA | | | 2-5 | 27-31-22 | D00675B | A04 | | | | D41773J | 22 | | | ALL |
| 0031 | 22 | GA | | | 2-5 | 27-31-22 | D00675B | A03 | | | | D41773J | 31 | | | ALL |
| 0032 | 22 | GA | | | 3-0 | 27-09-12 | D00711A | D07 | | | | TB0108Z | 7 | BJ | | ALL |
| 0033 | 22 | GA | | | 4-1 | 27-09-12 | D00351A | H04 | | | | TB0108Z | 7 | BJ | | ALL |
| 0034 | 22 | GA | | | 3-8 | 27-09-12 | D00675A | D06 | | | | TB0108Z | 7 | BJ | | ALL |
| 0035 | 22 | GA | | | 4-6 | 27-09-12 | D00669B | D10 | | | | TB0108Z | 7 | BJ | | ALL |
| 0036 | 22 | GA | | | 3-3 | 27-09-12 | D00667B | D02 | | | | TB0108Z | 7 | BJ | | ALL |
| 0037 | 22 | GA | | | 2-9 | 27-09-12 | D00665A | D01 | | | | TB0108Z | 7 | BJ | | ALL |
| 0038 | 22 | GA | | | 3-8 | 27-09-12 | D41773J | 12 | | | | TB0108Z | 7 | BJ | | ALL |
| 0039 | 22 | GA | | | 2-9 | 27-09-13 | D00665A | K13 | | | | TB0108Z | 8 | BJ | | ALL |
| 0040 | 22 | GA | | | 2-9 | 27-09-13 | D00665A | J13 | | | | TB0108Z | 9 | BJ | | ALL |
| 0041 | 22 | GA | | | 3-8 | 27-09-13 | D41773J | 13 | | | | TB0108Z | 8 | BJ | | ALL |
| 0042 | 22 | GA | | | 3-8 | 27-09-13 | D41773J | 14 | | | | TB0108Z | 9 | BJ | | ALL |
| 0043 | 22 | GA | | | 2-11 | 22-21-21 | D00351A | C05 | | | | GD01848 | DC.. | 2 | | ALL |
| 0044 | 22 | GA | | | 2-11 | 22-21-21 | D00351A | D05 | | | | GD01848 | DC.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 29

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 0045 | 22 | | GA | | 3-8 | 27-09-13 | D00675B | | H06 | | TB0108Z | 8 | BJ | | ALL |
| 0046 | 22 | | GA | | 3-8 | 27-09-13 | D00675B | | H05 | | TB0108Z | 9 | BJ | | ALL |
| 0047 | 22 | | GA | | 4-6 | 27-09-13 | D00669A | | K13 | | TB0108Z | 8 | BJ | | ALL |
| 0048 | 22 | | GA | | 4-6 | 27-09-13 | D00669A | | J13 | | TB0108Z | 9 | BJ | | ALL |
| 0049 | 22 | | GA | | 2-11 | 27-09-13 | D00667A | | K13 | | GD01843 | DC.. | 2 | | ALL |
| 0050 | 22 | | GA | | 2-5 | 27-09-11 | D40682J | | 2 | | D00671B | E15 | | | 001-099 |
| 0050 | 22 | | GA | | 2-6 | 27-09-11 | D40682J | | 2 | | D00671B | E15 | | | 115-199 |
| 0051 | 22 | | GA | | 2-4 | 27-09-11 | D00671B | | K15 | | TB0108Z | 10 | BJ | | ALL |
| 0052 | 22 | | GA | | 2-5 | 27-09-11 | D40682J | | 3 | | TB0108Z | 10 | BJ | | 001-099 |
| 0052 | 22 | | GA | | 3-3 | 27-09-11 | D40682J | | 3 | | TB0108Z | 10 | BJ | | 115-199 |
| 0053 | 22 | | GA | | 4-10 | 27-09-11 | D00673B | | K15 | | TB0108Z | 10 | BJ | | ALL |
| 0054 | 22 | | GA | | 0-7 | 27-61-15 | D00667A | | A02 | | D00667A | A03 | | | ALL |
| 0055 | 22 | | GA | | 0-7 | 27-61-15 | D00667B | | A03 | | D00667B | A04 | | | ALL |
| 0056 | 22 | | GA | | 0-7 | 27-61-15 | D00667B | | A11 | | D00667B | A12 | | | ALL |
| 0067 | 22 | | GA | | 2-0 | 22-21-21 | D00351A | | F15 | | D41793J | 21 | | | ALL |
| 0074 | 22 | | GA | | 3-4 | 22-21-21 | D00351A | | C01 | | D00671A | G01 | | | ALL |
| 0075 | 22 | | GA | | 3-4 | 22-21-21 | D00351A | | A01 | | D00671A | B08 | | | ALL |
| 0076 | 22 | | GA | | 3-4 | 22-21-21 | D00351A | | G04 | | D00671A | E03 | | | ALL |
| 0077 | 22 | | GA | | 3-4 | 22-21-21 | D00351A | | G05 | | D00671A | C05 | | | ALL |
| 0081 | 22 | | GA | | 2-4 | 22-21-21 | D00351A | | C02 | | D00673A | G01 | | | ALL |
| 0082 | 22 | | GA | | 2-4 | 22-21-21 | D00351A | | A02 | | D00673A | B08 | | | ALL |
| 0089 | 22 | | GA | | 2-2 | 27-21-22 | D00671A | | A08 | | D00711A | A01 | | | ALL |
| 0090 | 22 | | GA | | 2-2 | 27-21-22 | D00671A | | G03 | | D00711A | D01 | | | ALL |
| 0091 | 22 | | GA | | 3-6 | 27-21-22 | D00673A | | A08 | | D00711A | A02 | | | ALL |
| 0092 | 22 | | GA | | 3-6 | 27-21-22 | D00673A | | G03 | | D00711A | D02 | | | ALL |
| 0093 | 22 | | GA | | 2-3 | 27-21-22 | D00675A | | K15 | | D00711B | D08 | | | ALL |
| 0096 | 22 | | GA | | 4-1 | 27-21-22 | D00671A | | C10 | | D00673A | A10 | | | ALL |
| 0097 | 22 | | GA | | 4-10 | 27-21-22 | D00673A | | C12 | | TB0108Z | 14 | BJ | | ALL |
| 0098 | 22 | | GA | | 2-3 | 27-21-22 | D00711A | | D15 | | D41773J | 15 | | | ALL |
| 0099 | 22 | | GA | | 2-3 | 27-21-22 | D00711A | | A15 | | D41773J | 16 | | | ALL |
| 0100 | 22 | | GA | | 2-3 | 27-21-22 | D00711A | | B15 | | D41773J | 17 | | | ALL |
| 0101 | 22 | | GA | | 2-3 | 27-21-22 | D00711A | | C06 | | D41773J | 18 | | | ALL |
| 0102 | 22 | | GA | | 2-5 | 27-31-22 | D00675A | | A07 | | D41773J | 36 | | | ALL |
| 0103 | 22 | | GA | | 2-5 | 27-31-22 | D00675A | | A08 | | D41773J | 37 | | | ALL |
| 0104 | 22 | | GA | | 2-11 | 22-21-21 | D41773J | | 32 | | D00351A | H05 | | | ALL |
| 0105 | 22 | | GA | | 2-5 | 22-24-21 | D41773J | | 3 | | D00675A | C11 | | | ALL |
| 0106 | 22 | | GA | | 2-5 | 22-24-21 | D41773J | | 4 | | D00675A | A09 | | | ALL |
| 0107 | 22 | | GA | | 2-5 | 22-24-21 | D41773J | | 5 | | D00675A | A06 | | | ALL |
| 0108 | 22 | | GA | | 2-5 | 27-41-31 | D41773J | | 6 | | D00675A | B06 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 30

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | | 286N1165 | | | | E4-1 SHELF (continued) | | | | | | | | | |
| 0109 | 22 | GA | | | 2-5 | 22-22-21 | D00675A | J12 | | | D41773J | 8 | | | ALL |
| 0110 | 22 | GA | | | 4-1 | 22-21-21 | D00351B | K10 | | | TB0108Z | 10 | BJ | | ALL |
| 0111 | 22 | GA | | | 2-10 | 27-41-21 | D00675A | C04 | | | D00671A | G02 | | | ALL |
| 0112 | 22 | GA | | | 2-10 | 27-41-21 | D00675A | C05 | | | D00671A | A07 | | | ALL |
| 0113 | 22 | GA | | | 2-10 | 27-41-21 | D00675A | B04 | | | D00671A | B05 | | | ALL |
| 0114 | 22 | GA | | | 2-10 | 27-41-21 | D00675A | A04 | | | D00671A | E02 | | | ALL |
| 0115 | 22 | GA | | | 2-10 | 27-41-21 | D00673A | G02 | | | D00675A | E04 | | | ALL |
| 0116 | 22 | GA | | | 2-10 | 27-41-21 | D00673A | A07 | | | D00675A | E05 | | | ALL |
| 0117 | 22 | GA | | | 2-10 | 27-41-21 | D00673A | B05 | | | D00675A | B05 | | | ALL |
| 0118 | 22 | GA | | | 2-10 | 27-41-21 | D00673A | E02 | | | D00675A | A05 | | | ALL |
| 0119 | 22 | GA | | | 0-7 | 27-61-14 | D00665A | A04 | | | D00665A | B05 | | | ALL |
| 0120 | 22 | GA | | | 0-7 | 27-61-14 | D00665A | C03 | | | D00665A | D02 | | | ALL |
| 0123 | 22 | GA | | | 0-7 | 27-61-14 | D00665A | A03 | | | D00665A | A02 | | | ALL |
| 0124 | 22 | GA | | | 0-7 | 27-61-14 | D00665A | C06 | | | D00665A | C05 | | | ALL |
| 0126 | 22 | GA | | | 0-7 | 27-61-14 | D00665A | B02 | | | D00665A | B03 | | | ALL |
| 0127 | 22 | GA | | | 0-7 | 27-61-14 | D00665A | A08 | | | D00665A | C08 | | | ALL |
| 0130 | 22 | GA | | | 0-7 | 27-61-15 | D00667B | C07 | | | D00667B | C06 | | | ALL |
| 0131 | 22 | GA | | | 0-7 | 27-61-15 | D00667B | A05 | | | D00667B | B06 | | | ALL |
| 0133 | 22 | GA | | | 0-7 | 27-61-15 | D00667B | C04 | | | D00667B | D03 | | | ALL |
| 0134 | 22 | GA | | | 0-7 | 27-61-15 | D00667B | B03 | | | D00667B | B04 | | | ALL |
| 0135 | 22 | GA | | | 2-7 | 27-61-16 | D00669B | B14 | | | GD01851 | DC.. | 2 | | ALL |
| 0137 | 22 | GA | | | 0-7 | 27-61-16 | D00669B | D11 | | | D00669B | C11 | | | ALL |
| 0140 | 22 | GA | | | 0-7 | 27-61-16 | D00669B | C15 | | | D00669B | D14 | | | ALL |
| 0141 | 22 | GA | | | 2-4 | 22-21-21 | D00351A | B05 | | | D00673A | C05 | | | ALL |
| 0142 | 22 | GA | | | 2-4 | 22-21-21 | D00351A | A05 | | | D00673A | E03 | | | ALL |
| 0143 | 22 | GA | | | 2-11 | 22-21-21 | D00351A | E04 | | | GD01848 | DC.. | 2 | | ALL |
| 0144 | 22 | GA | | | 2-11 | 22-21-21 | D00351A | D04 | | | GD01848 | DC.. | 2 | | ALL |
| 0145 | 22 | GA | | | 2-11 | 22-21-21 | D00351A | C04 | | | GD01848 | DC.. | 2 | | ALL |
| 0146 | 22 | GA | | | 2-11 | 22-21-21 | D00351A | A04 | | | GD01848 | DC.. | 2 | | ALL |
| 0148Y | 22 | QB | | | 2-5 | 27-41-21 | D00675A | D04 | | | D41773J | 9 | | | ALL |
| 0149Y | 22 | QB | | | 2-5 | 27-41-21 | D00675A | D05 | | | D41773J | 10 | | | ALL |
| 0150 | 22 | GA | | | 2-6 | 27-41-21 | D41773J | 2 | | | TB0108Y | C044 | BJ | | ALL |
| 0151 | 22 | GA | | | 2-6 | 27-41-21 | D00675A | C09 | | | TB0108Y | C044 | BJ | | ALL |
| 0152 | 22 | GA | | | 2-5 | 27-41-21 | D00675A | C12 | | | D41773J | 11 | | | ALL |
| 0153 | 22 | GA | | | 2-10 | 27-41-21 | D41793J | 28 | | | TB0108Y | C044 | BJ | | ALL |
| 0154 | 22 | GA | | | 2-2 | 27-41-21 | D00809 | X1 | | | TB0108Y | A056 | BJ | | ALL |
| 0155 | 22 | GA | | | 1-11 | 27-41-21 | D00809 | X2 | | | D41367J | 46 | | | ALL |
| 0156Y | 22 | QB | | | 2-0 | 27-41-21 | D00809 | A3 | | | D41843J | 3 | | | ALL |
| 0157Y | 22 | QB | | | 2-0 | 27-41-21 | D00809 | A1 | | | D41843J | 4 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 31

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 0158Y | 22 | | QB | | 2-0 | 27-41-21 | D00809 | | A2 | | D41707J | | 1 | | ALL |
| 0161 | 22 | | GA | | 2-2 | 27-61-12 | D00669B | | J09 | | GD01853 | DC.. | 2 | | 003-099 |
| 0162 | 22 | | GA | | 3-3 | 27-61-12 | D00667B | | E09 | | GD01853 | DC.. | 2 | | 003-099 |
| 0163 | 22 | | GA | | 3-10 | 27-61-12 | D00665B | | A09 | | GD01853 | DC.. | 2 | | 003-099 |
| 0201 | 22 | | GA | | 3-10 | 27-48-11 | D41918J | | 15 | | TB0108Y | A057 | BJ | | ALL |
| 0202 | 22 | | GA | | 2-8 | 27-48-11 | D41843J | | 13 | | TB0108Y | A057 | BJ | | ALL |
| 0203 | 22 | | GA | | 2-8 | 27-48-11 | D41707J | | 10 | | TB0108Y | A057 | BJ | | ALL |
| 0204 | 22 | | GA | | 1-8 | 27-48-11 | D41707J | | 11 | | D41843J | | 14 | | ALL |
| 0205 | 22 | | GA | | 1-8 | 27-48-11 | D41707J | | 12 | | D41843J | | 15 | | ALL |
| 0206 | 22 | | GA | | 2-5 | 27-09-14 | D41367J | | 44 | | TB0108Y | A049 | BJ | | ALL |
| 0207 | 22 | | GA | | 2-7 | 27-09-14 | D41367J | | 49 | | TB0108Y | A062 | BJ | | ALL |
| 0208 | 22 | | GA | | 1-11 | 27-61-14 | D00671A | | C14 | | D00665B | | G06 | | ALL |
| 0209 | 22 | | GA | | 1-11 | 27-61-14 | D00671A | | K12 | | D00665B | | G04 | | ALL |
| 0210 | 22 | | GA | | 4-1 | 27-61-14 | D00671B | | G01 | | D00673B | | E01 | | ALL |
| 0211 | 22 | | GA | | 3-8 | 27-61-14 | D00673B | | C01 | | TB0108Z | | 46 | BJ | ALL |
| 0212 | 22 | | GA | | 3-9 | 27-61-14 | D00673A | | K12 | | D00665B | | F04 | | ALL |
| 0213 | 22 | | GA | | 3-9 | 27-61-14 | D00673A | | C14 | | D00665B | | F06 | | ALL |
| 0214 | 22 | | GA | | 2-7 | 27-09-14 | D41367J | | 50 | | TB0108Y | A063 | BJ | | ALL |
| 0215 | 22 | | GA | | 1-11 | 27-61-14 | TB0108Z | | 59 | BJ | D00665A | | A15 | | ALL |
| 0216 | 22 | | GA | | 2-6 | 27-61-15 | D00671A | | C15 | | D00667B | | G14 | | ALL |
| 0217 | 22 | | GA | | 2-6 | 27-61-15 | D00671A | | K13 | | D00667B | | G12 | | ALL |
| 0218 | 22 | | GA | | 2-7 | 27-09-14 | D41367J | | 48 | | TB0108Y | C062 | BJ | | ALL |
| 0219 | 22 | | GA | | 3-2 | 27-61-15 | D00673A | | C15 | | D00667B | | F14 | | ALL |
| 0220 | 22 | | GA | | 3-2 | 27-61-15 | D00673A | | K13 | | D00667B | | F12 | | ALL |
| 0222 | 22 | | GA | | 2-2 | 27-61-15 | TB0108Z | | 59 | BJ | D00667A | | A15 | | ALL |
| 0223 | 22 | | GA | | 3-9 | 27-61-16 | D00671A | | F13 | | D00669A | | E11 | | ALL |
| 0224 | 22 | | GA | | 3-9 | 27-61-16 | D00671A | | J12 | | D00669A | | G03 | | ALL |
| 0225 | 22 | | GA | | 3-9 | 27-61-16 | D00671A | | B14 | | D00669A | | G05 | | ALL |
| 0226 | 22 | | GA | | 1-11 | 27-61-15 | D41367J | | 41 | | D00667B | | H12 | | ALL |
| 0227 | 22 | | GA | | 2-5 | 27-61-15 | D41367J | | 42 | | GD01848 | DC.. | 2 | | ALL |
| 0228 | 22 | | GA | | 1-11 | 27-61-16 | D00673A | | B14 | | D00669A | | F05 | | ALL |
| 0229 | 22 | | GA | | 1-11 | 27-61-16 | D00673A | | J12 | | D00669A | | F03 | | ALL |
| 0230 | 22 | | GA | | 1-11 | 27-61-16 | D00673A | | F13 | | D00669A | | E12 | | ALL |
| 0231 | 22 | | GA | | 3-5 | 27-61-16 | TB0108Z | | 59 | BJ | D00669A | | A15 | | ALL |
| 0232 | 22 | | GA | | 2-5 | 27-09-12 | D41367J | | 8 | | TB0108Z | | 47 | BJ | ALL |
| 0233 | 22 | | GA | | 2-4 | 27-09-12 | D41777J | | 7 | | TB0108Z | | 47 | BJ | ALL |
| 0234 | 22 | | GA | | 1-10 | 27-09-12 | D00711B | | D07 | | TB0108Z | | 47 | BJ | ALL |
| 0235 | 22 | | GA | | 2-11 | 27-09-12 | D00351B | | H04 | | TB0108Z | | 47 | BJ | ALL |
| 0236 | 22 | | GA | | 2-6 | 27-09-12 | D00675A | | E14 | | TB0108Z | | 47 | BJ | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 32

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | | 286N1165 | | | | E4-1 SHELF (continued) | | | | | | | | | |
| 0237 | 22 | GA | | | 3-4 | 27-09-12 | D00669A | D01 | | | TB0108Z | 47 | BJ | | ALL |
| 0238 | 22 | GA | | | 2-1 | 27-09-12 | D00667B | D10 | | | TB0108Z | 47 | BJ | | ALL |
| 0239 | 22 | GA | | | 1-10 | 27-09-12 | D00665B | D02 | | | TB0108Z | 47 | BJ | | ALL |
| 0240 | 22 | GA | | | 2-5 | 27-09-14 | D41367J | 43 | | | TB0108Z | 48 | BJ | | ALL |
| 0241 | 22 | GA | | | 2-3 | 27-09-14 | D00671B | A13 | | | TB0108Y | A049 | BJ | | ALL |
| 0242 | 22 | GA | | | 1-11 | 27-09-14 | D00711B | D14 | | | TB0108Y | A063 | BJ | | ALL |
| 0243 | 22 | GA | | | 3-1 | 27-09-14 | D00351B | F04 | | | TB0108Y | C062 | BJ | | ALL |
| 0244 | 22 | GA | | | 2-7 | 27-09-14 | D00675B | F04 | | | TB0108Y | A062 | BJ | | ALL |
| 0245 | 22 | GA | | | 3-4 | 27-09-14 | D00669A | C13 | | | TB0108Z | 48 | BJ | | ALL |
| 0246 | 22 | GA | | | 2-1 | 27-09-14 | D00667A | C13 | | | TB0108Z | 48 | BJ | | ALL |
| 0247 | 22 | GA | | | 1-10 | 27-09-14 | D00665A | C13 | | | TB0108Z | 48 | BJ | | ALL |
| 0248 | 22 | GA | | | 3-8 | 27-09-14 | D00673B | A13 | | | TB0108Y | A049 | BJ | | ALL |
| 0250 | 22 | GA | | | 3-9 | 27-61-12 | D41862J | 4 | | | TB0108Z | 51 | BJ | | ALL |
| 0251 | 22 | GA | | | 2-4 | 27-61-12 | D41777J | 22 | | | TB0108Z | 51 | BJ | | ALL |
| 0252 | 22 | GA | | | 3-4 | 27-61-12 | D00669A | B13 | | | TB0108Z | 51 | BJ | | ALL |
| 0253 | 22 | GA | | | 2-1 | 27-61-12 | D00667A | B13 | | | TB0108Z | 51 | BJ | | ALL |
| 0254 | 22 | GA | | | 1-10 | 27-61-12 | D00665A | B13 | | | TB0108Z | 51 | BJ | | ALL |
| 0255 | 22 | GA | | | 2-4 | 27-09-13 | D00665A | A12 | | | GD01843 | DC.. | 2 | | ALL |
| 0256 | 22 | GA | | | 2-7 | 27-09-13 | D00669A | A12 | | | GD01851 | DC.. | 2 | | ALL |
| 0257 | 22 | GA | | | 2-4 | 27-09-13 | D41777J | 8 | | | TB0108Y | A050 | BJ | | ALL |
| 0258 | 22 | GA | | | 2-4 | 27-09-13 | D41777J | 9 | | | TB0108Y | C050 | BJ | | ALL |
| 0259 | 22 | GA | | | 2-5 | 27-09-13 | D41367J | 6 | | | TB0108Y | C050 | BJ | | ALL |
| 0260 | 22 | GA | | | 2-5 | 27-09-13 | D41367J | 7 | | | TB0108Y | A050 | BJ | | ALL |
| 0261 | 22 | GA | | | 3-1 | 27-09-13 | D00711B | A03 | | | GD01842 | DC.. | 2 | | ALL |
| 0262 | 22 | GA | | | 1-10 | 27-09-13 | D00711B | B03 | | | TB0108Y | C050 | BJ | | ALL |
| 0263 | 22 | GA | | | 2-1 | 27-09-13 | D00667A | A12 | | | TB0108Y | A050 | BJ | | ALL |
| 0264 | 22 | GA | | | 2-1 | 27-09-13 | D00667A | A13 | | | TB0108Y | C050 | BJ | | ALL |
| 0265 | 22 | GA | | | 2-4 | 27-09-11 | D00671B | A15 | | | TB0108Z | 59 | BJ | | ALL |
| 0266 | 22 | GA | | | 2-4 | 27-09-11 | D41918J | 1 | | | D00673B | E15 | | | ALL |
| 0267 | 22 | GA | | | 3-10 | 27-09-11 | D41918J | 2 | | | TB0108Z | 59 | BJ | | ALL |
| 0268 | 22 | GA | | | 3-9 | 27-09-11 | D00673B | A15 | | | TB0108Z | 59 | BJ | | ALL |
| 0269Y | 20 | QB | | | 2-7 | 27-41-21 | D42020J | 1 | | | D41843J | 1 | | | ALL |
| 0270Y | 20 | QB | | | 2-7 | 27-41-21 | D42020J | 2 | | | D41843J | 2 | | | ALL |
| 0272Y | 22 | QB | | | 2-1 | 27-41-21 | D41707J | 2 | | | D00675A | F09 | | | ALL |
| 0274Y | 22 | QB | | | 1-8 | 27-41-21 | D41707J | 4 | | | D41843J | 5 | | | ALL |
| 0276Y | 22 | QB | | | 2-1 | 27-41-21 | D41707J | 6 | | | D00675A | F10 | | | ALL |
| 0277Y | 22 | QB | | | 1-11 | 27-41-21 | D00675A | C08 | | | D41793J | 26 | | | ALL |
| 0278Y | 22 | QB | | | 1-11 | 27-41-21 | D00675A | C07 | | | D41793J | 27 | | | ALL |
| 0283 | 22 | GA | | | 2-4 | 27-09-14 | D41777J | 21 | | | TB0108Z | 48 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 33

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 0283 | 22 | | GA | | 2-4 | 27-09-14 | D41777J | | 48 | | TB0108Z | 48 | BJ | | 115-199 |
| 0284 | 22 | | GA | | 2-6 | 27-09-14 | D41777J | | 18 | | TB0108Y | A062 | BJ | | 001-099 |
| 0284 | 22 | | GA | | 2-6 | 27-09-14 | D41777J | | 45 | | TB0108Y | A062 | BJ | | 115-199 |
| 0285 | 22 | | GA | | 3-4 | 22-21-21 | D00351B | | A01 | | D00671A | B15 | | | ALL |
| 0286 | 22 | | GA | | 2-6 | 27-09-14 | D41777J | | 19 | | TB0108Y | C062 | BJ | | 001-099 |
| 0286 | 22 | | GA | | 2-6 | 27-09-14 | D41777J | | 46 | | TB0108Y | C062 | BJ | | 115-199 |
| 0287 | 22 | | GA | | 2-6 | 27-09-14 | D41777J | | 20 | | TB0108Y | A063 | BJ | | 001-099 |
| 0287 | 22 | | GA | | 2-6 | 27-09-14 | D41777J | | 47 | | TB0108Y | A063 | BJ | | 115-199 |
| 0288 | 22 | | GA | | 2-4 | 22-21-21 | D00351B | | C02 | | D00673A | J13 | | | ALL |
| 0289 | 22 | | GA | | 2-4 | 22-21-21 | D00351B | | A02 | | D00673A | B15 | | | ALL |
| 0292 | 22 | | GA | | 3-4 | 22-21-21 | D00351B | | C01 | | D00671A | J13 | | | ALL |
| 0293 | 22 | | GA | | 2-2 | 27-21-22 | D00671A | | A15 | | D00711B | A12 | | | ALL |
| 0294 | 22 | | GA | | 2-2 | 27-21-22 | D00671A | | H13 | | D00711B | D12 | | | ALL |
| 0295 | 22 | | GA | | 3-6 | 27-21-22 | D00673A | | A15 | | D00711B | A13 | | | ALL |
| 0296 | 22 | | GA | | 3-6 | 27-21-22 | D00673A | | H13 | | D00711B | D13 | | | ALL |
| 0297 | 22 | | GA | | 2-4 | 27-31-22 | D00675A | | E07 | | D41777J | 35 | | | ALL |
| 0298 | 22 | | GA | | 2-4 | 27-31-22 | D00675A | | E08 | | D41777J | 36 | | | ALL |
| 0299 | 22 | | GA | | 2-5 | 22-21-21 | D41862J | | 2 | | D00351B | G08 | | | ALL |
| 0300 | 22 | | GA | | 2-5 | 22-21-21 | D41862J | | 1 | | D00351B | G07 | | | ALL |
| 0301 | 22 | | GA | | 3-9 | 22-21-21 | D41862J | | 3 | | TB0108Y | C049 | BJ | | ALL |
| 0302 | 22 | | GA | | 2-11 | 22-21-21 | D00351B | | F07 | | TB0108Y | C049 | BJ | | ALL |
| 0303 | 22 | | GA | | 2-4 | 22-21-21 | D41777J | | 31 | | TB0108Y | C049 | BJ | | ALL |
| 0304 | 22 | | GA | | 2-9 | 22-21-21 | D41777J | | 32 | | D00351B | F08 | | | ALL |
| 0305 | 22 | | GA | | 2-6 | 22-21-21 | D41367J | | 13 | | TB0108Y | A054 | BJ | | ALL |
| 0306 | 22 | | GA | | 3-0 | 22-21-21 | D00351B | | H05 | | TB0108Y | A054 | BJ | | ALL |
| 0307 | 22 | | GA | | 2-5 | 22-21-21 | D41777J | | 24 | | TB0108Y | A054 | BJ | | ALL |
| 0308 | 22 | | GA | | 2-5 | 22-24-21 | D41777J | | 1 | | TB0108Y | C054 | BJ | | ALL |
| 0309 | 22 | | GA | | 3-0 | 22-21-21 | D00351B | | A04 | | TB0108Z | 59 | BJ | | ALL |
| 0310 | 22 | | GA | | 2-7 | 22-24-21 | D00675A | | C14 | | TB0108Y | C054 | BJ | | ALL |
| 0311 | 22 | | GA | | 2-6 | 22-24-21 | D41367J | | 22 | | TB0108Y | C054 | BJ | | ALL |
| 0312 | 22 | | GA | | 2-4 | 22-24-21 | D41777J | | 23 | | D00675A | F11 | | | ALL |
| 0313 | 22 | | GA | | 2-4 | 22-24-21 | D41777J | | 34 | | D00675A | E11 | | | ALL |
| 0314 | 22 | | GA | | 2-4 | 22-22-21 | D00675B | | B05 | | D41777J | 33 | | | ALL |
| 0315 | 22 | | GA | | 2-0 | 22-22-21 | D00675A | | D10 | | D41367J | 18 | | | ALL |
| 0316 | 22 | | GA | | 2-0 | 22-22-21 | D00675A | | D09 | | D41367J | 14 | | | ALL |
| 0317 | 22 | | GA | | 2-2 | 27-21-12 | D41777J | | 10 | | D00711B | D04 | | | ALL |
| 0318 | 22 | | GA | | 2-2 | 27-21-12 | D41777J | | 11 | | D00711B | C08 | | | ALL |
| 0319 | 22 | | GA | | 2-2 | 27-21-12 | D41777J | | 12 | | D00711B | A01 | | | ALL |
| 0320 | 22 | | GA | | 2-2 | 27-21-12 | D41777J | | 13 | | D00711B | D01 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 34

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | | 286N1165 | | | | E4-1 SHELF (continued) | | | | | | | | | |
| 0321 | 22 | GA | | | 2-2 | 27-21-12 | D41777J | | 14 | | D00711B | B01 | | | ALL |
| 0322 | 22 | GA | | | 2-10 | 27-41-21 | D00675A | | G13 | | D00671A | H12 | | | ALL |
| 0323 | 22 | GA | | | 2-10 | 27-41-21 | D00675A | | G14 | | D00671A | A14 | | | ALL |
| 0324 | 22 | GA | | | 2-10 | 27-41-21 | D00673A | | H12 | | D00675A | J13 | | | ALL |
| 0325 | 22 | GA | | | 2-10 | 27-41-21 | D00673A | | A14 | | D00675A | J14 | | | ALL |
| 0326 | 22 | GA | | | 0-7 | 27-61-16 | D00669A | | A08 | | D00669A | C08 | | | ALL |
| 0328 | 22 | GA | | | 0-7 | 27-61-14 | D00665B | | A04 | | D00665B | A03 | | | ALL |
| 0329 | 22 | GA | | | 0-7 | 27-61-14 | D00665B | | C07 | | D00665B | C06 | | | ALL |
| 0330 | 22 | GA | | | 0-7 | 27-61-14 | D00665B | | A05 | | D00665B | B06 | | | ALL |
| 0331 | 22 | GA | | | 0-7 | 27-61-14 | D00665B | | C04 | | D00665B | D03 | | | ALL |
| 0333 | 22 | GA | | | 0-7 | 27-61-14 | D00665B | | B03 | | D00665B | B04 | | | ALL |
| 0334 | 22 | GA | | | 0-7 | 27-61-15 | D00667B | | A13 | | D00667B | B14 | | | ALL |
| 0339 | 22 | GA | | | 0-7 | 27-61-15 | D00667B | | C15 | | D00667B | C14 | | | ALL |
| 0340 | 22 | GA | | | 0-7 | 27-61-15 | D00667B | | C12 | | D00667B | D11 | | | ALL |
| 0341 | 22 | GA | | | 0-7 | 27-61-15 | D00667B | | B11 | | D00667B | B12 | | | ALL |
| 0342 | 22 | GA | | | 0-7 | 27-61-16 | D00669A | | D02 | | D00669A | C02 | | | ALL |
| 0346 | 22 | GA | | | 0-7 | 27-61-16 | D00669A | | C06 | | D00669A | D05 | | | ALL |
| 0347Y | 22 | QB | | | 2-4 | 27-41-21 | D00675A | | E12 | | D41777J | 6 | | | ALL |
| 0348Y | 22 | QB | | | 3-10 | 27-41-21 | D41918J | | 9 | | TB0108Y | A056 | BJ | | ALL |
| 0349Y | 22 | QB | | | 2-7 | 27-41-21 | D00675A | | F07 | | TB0108Y | A056 | BJ | | ALL |
| 0350Y | 22 | QB | | | 2-7 | 27-41-21 | D00675A | | F08 | | TB0108Y | A056 | BJ | | ALL |
| 0351Y | 22 | QB | | | 2-7 | 27-41-21 | D00675A | | A13 | | TB0108Y | A058 | BJ | | ALL |
| 0352Y | 22 | QB | | | 2-7 | 27-41-21 | D00675A | | A14 | | TB0108Y | C058 | BJ | | ALL |
| 0353 | 22 | GA | | | 2-4 | 27-41-21 | D00675A | | F12 | | D41777J | 4 | | | ALL |
| 0354 | 22 | GA | | | 2-5 | 22-21-21 | D41367J | | 9 | | TB0108Y | C049 | BJ | | ALL |
| 0355 | 22 | GA | | | 2-4 | 22-21-21 | D00351A | | H15 | | D41791J | 3 | | | ALL |
| 0356 | 22 | GA | | | 4-8 | 27-61-16 | D00669A | | B05 | | GD01842 | DC.. | 2 | | ALL |
| 0363Y | 22 | QB | | | 2-8 | 27-41-21 | D41707J | | 7 | | TB0108Y | A058 | BJ | | ALL |
| 0364Y | 22 | QB | | | 2-8 | 27-41-21 | D41707J | | 8 | | TB0108Y | C058 | BJ | | ALL |
| 0365Y | 22 | QB | | | 2-5 | 27-41-21 | D41777J | | 2 | | TB0108Y | A058 | BJ | | ALL |
| 0366Y | 22 | QB | | | 2-5 | 27-41-21 | D41777J | | 3 | | TB0108Y | C058 | BJ | | ALL |
| 0367 | 22 | GA | | | 3-5 | 27-32-21 | D41707J | | 17 | | D41918J | 7 | | | ALL |
| 0368 | 22 | GA | | | 2-8 | 27-32-21 | D41707J | | 18 | | TB0108Y | A061 | BJ | | 001-099 |
| 0368 | 24 | GK | | | 2-8 | 27-32-21 | D41707J | | 18 | | TB0108Y | A061 | BJ | | 115-199 |
| 0369 | 22 | GA | | | 2-3 | 27-09-14 | D41367J | | 51 | | D41777J | 17 | | | 001-099 |
| 0369 | 22 | GA | | | 2-3 | 27-09-14 | D41367J | | 51 | | D41777J | 44 | | | 115-199 |
| 0370 | 24 | GK | | | 1-7 | 31-51-42 | D41707J | | 20 | | D41367J | 4 | | | ALL |
| 0371 | 24 | GK | | | 1-7 | 31-51-41 | D41707J | | 21 | | D41367J | 32 | | | ALL |
| 0375 | 24 | GK | | | 2-5 | 31-31-62 | D00351B | | H10 | | D41367J | 37 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 35

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 0375 | 24 | | GK | | 2-5 | 31-31-32 | D41367J | | 37 | | D00351B | | H10 | | 115-199 |
| 0376 | 24 | | GK | | 2-6 | 31-31-62 | D00665A | | H13 | | D41367J | | 38 | | 001-099 |
| 0376 | 24 | | GK | | 2-6 | 31-31-32 | D41367J | | 38 | | D00665A | | H13 | | 115-199 |
| 0377 | 24 | | GK | | 1-11 | 31-31-62 | D00667A | | H13 | | D41367J | | 39 | | 001-099 |
| 0377 | 24 | | GK | | 1-11 | 31-31-32 | D41367J | | 39 | | D00667A | | H13 | | 115-199 |
| 0378 | 24 | | GK | | 2-11 | 31-31-62 | D00669A | | H13 | | D41367J | | 40 | | 001-099 |
| 0378 | 24 | | GK | | 2-11 | 31-31-32 | D41367J | | 40 | | D00669A | | H13 | | 115-199 |
| 0380 | 22 | | GA | | 2-0 | 27-41-21 | D00675A | | B13 | | D41367J | | 33 | | ALL |
| 0381 | 22 | | GA | | 2-0 | 27-41-21 | D00675A | | B14 | | D41367J | | 34 | | ALL |
| 0382 | 22 | | GA | | 2-3 | 27-41-21 | D41777J | | 26 | | D41367J | | 36 | | 001-099 |
| 0382 | 22 | | GA | | 2-3 | 27-41-21 | D41777J | | 43 | | D41367J | | 36 | | 115-199 |
| 0383 | 22 | | GA | | 2-3 | 27-41-21 | D41777J | | 25 | | D41367J | | 35 | | 001-099 |
| 0383 | 22 | | GA | | 2-3 | 27-41-21 | D41777J | | 42 | | D41367J | | 35 | | 115-199 |
| 0384 | 22 | | GA | | 2-7 | 27-32-21 | D41367J | | 25 | | TB0108Y | A061 | BJ | | 001-099 |
| 0384 | 24 | | GK | | 2-7 | 27-32-21 | D41367J | | 25 | | TB0108Y | A061 | BJ | | 115-199 |
| 0385 | 22 | | GA | | 2-7 | 27-32-21 | D41367J | | 2 | | TB0108Y | A061 | BJ | | 001-099 |
| 0385 | 24 | | GK | | 2-7 | 27-32-21 | D41367J | | 2 | | TB0108Y | A061 | BJ | | 115-199 |
| 0401 | 22 | | GA | | 3-9 | 27-61-14 | D00673B | | H03 | | D00665B | | F14 | | ALL |
| 0402 | 22 | | GA | | 3-9 | 27-61-14 | D00673B | | F03 | | D00665B | | F12 | | ALL |
| 0404 | 16 | | GA | | 2-9 | 27-61-14 | D00665C | | 8 | | GD01841 | DC.. | 2 | | ALL |
| 0405 | 16 | | GA | | 2-9 | 27-61-14 | D00665C | | 3 | | GD01841 | DC.. | 2 | | ALL |
| 0406 | 16 | | GA | | 2-9 | 27-61-14 | D00665C | | 2 | | GD01841 | DC.. | 2 | | ALL |
| 0407 | 16 | | GA | | 2-9 | 27-61-14 | D00665C | | 7 | | GD01841 | DC.. | 2 | | ALL |
| 0408 | 16 | | GA | | 2-9 | 27-61-14 | D00665C | | 10 | | GD01841 | DC.. | 2 | | ALL |
| 0409 | 16 | | GA | | 2-9 | 27-61-14 | D00665C | | 9 | | GD01841 | DC.. | 2 | | ALL |
| 0410 | 22 | | GA | | 1-11 | 27-61-14 | D00671B | | F03 | | D00665B | | G12 | | ALL |
| 0411 | 22 | | GA | | 1-11 | 27-61-14 | D00671B | | H03 | | D00665B | | G14 | | ALL |
| 0413 | 22 | | GA | | 2-6 | 27-61-15 | D00671B | | F04 | | D00667A | | G03 | | ALL |
| 0414 | 22 | | GA | | 2-6 | 27-61-15 | D00671B | | H04 | | D00667A | | G05 | | ALL |
| 0416 | 22 | | GA | | 2-6 | 27-61-15 | D00671B | | K01 | | D00667A | | E11 | | ALL |
| 0417 | 22 | | GA | | 3-2 | 27-61-15 | D00673B | | K01 | | D00667A | | E12 | | ALL |
| 0419 | 22 | | GA | | 3-2 | 27-61-15 | D00673B | | H04 | | D00667A | | F05 | | ALL |
| 0420 | 22 | | GA | | 3-2 | 27-61-15 | D00673B | | F04 | | D00667A | | F03 | | ALL |
| 0421 | 16 | | GA | | 2-11 | 27-61-15 | D00667C | | 8 | | GD01844 | DC.. | 2 | | ALL |
| 0422 | 16 | | GA | | 2-11 | 27-61-15 | D00667C | | 3 | | GD01844 | DC.. | 2 | | ALL |
| 0423 | 16 | | GA | | 2-11 | 27-61-15 | D00667C | | 2 | | GD01844 | DC.. | 2 | | ALL |
| 0424 | 16 | | GA | | 2-11 | 27-61-15 | D00667C | | 7 | | GD01844 | DC.. | 2 | | ALL |
| 0429 | 22 | | GA | | 3-9 | 27-61-16 | D00671B | | H05 | | D00669B | | G06 | | ALL |
| 0430 | 22 | | GA | | 3-9 | 27-61-16 | D00671B | | F05 | | D00669B | | G04 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 36

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 0431 | 22 | | GA | | 4-1 | 27-61-16 | D00671B | | C07 | | D00673B | A07 | | | ALL |
| 0432 | 22 | | GA | | 3-0 | 27-61-16 | D00673B | | C05 | | TB0108Z | 86 | BJ | | ALL |
| 0433 | 22 | | GA | | 1-11 | 27-61-16 | D00673B | | F05 | | D00669B | F04 | | | ALL |
| 0434 | 22 | | GA | | 1-11 | 27-61-16 | D00673B | | H05 | | D00669B | F06 | | | ALL |
| 0436 | 16 | | GA | | 3-0 | 27-61-16 | D00669C | | 8 | | GD01850 | DC.. | 2 | | ALL |
| 0437 | 16 | | GA | | 3-0 | 27-61-16 | D00669C | | 3 | | GD01850 | DC.. | 2 | | ALL |
| 0438 | 16 | | GA | | 3-0 | 27-61-16 | D00669C | | 2 | | GD01850 | DC.. | 2 | | ALL |
| 0439 | 16 | | GA | | 3-0 | 27-61-16 | D00669C | | 7 | | GD01850 | DC.. | 2 | | ALL |
| 0443 | 22 | | GA | | 2-5 | 27-09-11 | D00671C | | 5 | | GD01840 | AC.. | 2 | | ALL |
| 0444 | 16 | | GA | | 2-5 | 27-09-11 | D00671C | | 10 | | GD01840 | DC.. | 2 | | ALL |
| 0445 | 16 | | GA | | 2-5 | 27-09-11 | D00671C | | 9 | | GD01840 | DC.. | 2 | | ALL |
| 0446 | 16 | | GA | | 2-5 | 27-09-11 | D00671C | | 2 | | GD01840 | DC.. | 2 | | ALL |
| 0447 | 16 | | GA | | 2-5 | 27-09-11 | D00671C | | 7 | | GD01840 | DC.. | 2 | | ALL |
| 0448 | 16 | | GA | | 2-5 | 27-09-11 | D00671C | | 3 | | GD01840 | DC.. | 2 | | ALL |
| 0449 | 16 | | GA | | 2-5 | 27-09-11 | D00671C | | 11 | | GD01840 | AC.. | 2 | | ALL |
| 0450 | 16 | | GA | | 2-5 | 27-09-11 | D00671C | | 8 | | GD01840 | ST.. | 2 | | ALL |
| 0451 | 16 | | GA | | 2-11 | 27-09-11 | D00673C | | 10 | | GD01852 | DC.. | 2 | | ALL |
| 0452 | 16 | | GA | | 2-11 | 27-09-11 | D00673C | | 9 | | GD01852 | DC.. | 2 | | ALL |
| 0453 | 16 | | GA | | 2-6 | 27-09-11 | D00673C | | 2 | | GD01853 | DC.. | 2 | | ALL |
| 0454 | 16 | | GA | | 2-11 | 27-09-11 | D00673C | | 7 | | GD01852 | DC.. | 2 | | ALL |
| 0455 | 16 | | GA | | 2-11 | 27-09-11 | D00673C | | 3 | | GD01852 | DC.. | 2 | | ALL |
| 0456 | 16 | | GA | | 2-11 | 27-09-11 | D00673C | | 11 | | GD01852 | AC.. | 2 | | ALL |
| 0457 | 16 | | GA | | 2-11 | 27-09-11 | D00673C | | 8 | | GD01852 | ST.. | 2 | | ALL |
| 0458 | 22 | | GA | | 2-5 | 27-09-12 | D41781J | | 12 | | TB0108Z | 87 | BJ | | ALL |
| 0459 | 22 | | GA | | 2-4 | 27-09-12 | D00351B | | C14 | | TB0108Y | A090 | BJ | | ALL |
| 0460 | 22 | | GA | | 2-0 | 27-09-12 | D00675B | | K12 | | TB0108Y | A090 | BJ | | ALL |
| 0461 | 22 | | GA | | 2-8 | 27-09-12 | D00669B | | D02 | | TB0108Z | 87 | BJ | | ALL |
| 0462 | 22 | | GA | | 2-4 | 27-09-12 | D00667A | | D01 | | TB0108Z | 87 | BJ | | ALL |
| 0463 | 22 | | GA | | 2-10 | 27-09-12 | D00665B | | D10 | | TB0108Z | 87 | BJ | | ALL |
| 0464 | 22 | | GA | | 3-1 | 27-21-22 | D00711B | | C15 | | GD01842 | DC.. | 2 | | ALL |
| 0465 | 22 | | GA | | 3-1 | 27-21-22 | D00711B | | B15 | | GD01842 | DC.. | 2 | | ALL |
| 0466 | 16 | | GA | | 3-1 | 27-21-22 | D00711C | | 3 | | GD01842 | DC.. | 2 | | ALL |
| 0467 | 16 | | GA | | 3-1 | 27-21-22 | D00711C | | 4 | | GD01842 | DC.. | 2 | | ALL |
| 0468 | 16 | | GA | | 3-1 | 27-21-22 | D00711C | | 2 | | GD01842 | ST.. | 2 | | ALL |
| 0469 | 22 | | GA | | 2-3 | 22-21-21 | D41781J | | 11 | | D00351B | C15 | | | ALL |
| 0470 | 22 | | GA | | 2-3 | 22-24-21 | D41781J | | 1 | | D00675B | H15 | | | ALL |
| 0471 | 22 | | GA | | 2-3 | 22-22-21 | D00675B | | J15 | | D41781J | 2 | | | ALL |
| 0472 | 22 | | GA | | 2-3 | 22-22-21 | D00675B | | J14 | | D41781J | 3 | | | ALL |
| 0473 | 22 | | GA | | 2-3 | 22-22-21 | D00675A | | G12 | | D41781J | 4 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 37

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 0474 | 22 | | GA | | 0-7 | 27-61-14 | D00665B | A13 | | | D00665B | B14 | | | ALL |
| 0475 | 22 | | GA | | 0-7 | 27-61-14 | D00665B | C12 | | | D00665B | D11 | | | ALL |
| 0478 | 22 | | GA | | 0-7 | 27-61-14 | D00665B | A12 | | | D00665B | A11 | | | ALL |
| 0479 | 22 | | GA | | 0-7 | 27-61-14 | D00665B | C15 | | | D00665B | C14 | | | ALL |
| 0481 | 22 | | GA | | 0-7 | 27-61-14 | D00665B | B11 | | | D00665B | B12 | | | ALL |
| 0482 | 20 | | GA | | 2-9 | 27-61-14 | D00665C | 6 | | | GD01841 | DC.. | 2 | | ALL |
| 0483 | 20 | | GA | | 2-9 | 27-61-14 | D00665C | 5 | | | GD01841 | DC.. | 2 | | ALL |
| 0484 | 22 | | GA | | 0-7 | 27-61-15 | D00667A | A04 | | | D00667A | B05 | | | ALL |
| 0489 | 22 | | GA | | 0-7 | 27-61-15 | D00667A | C06 | | | D00667A | C05 | | | ALL |
| 0490 | 22 | | GA | | 0-7 | 27-61-15 | D00667A | C03 | | | D00667A | D02 | | | ALL |
| 0491 | 22 | | GA | | 0-7 | 27-61-15 | D00667A | B02 | | | D00667A | B03 | | | ALL |
| 0492 | 16 | | GA | | 2-11 | 27-61-15 | D00667C | 10 | | | GD01844 | DC.. | 2 | | ALL |
| 0493 | 16 | | GA | | 2-11 | 27-61-15 | D00667C | 9 | | | GD01844 | DC.. | 2 | | ALL |
| 0494 | 20 | | GA | | 2-11 | 27-61-15 | D00667C | 6 | | | GD01844 | DC.. | 2 | | ALL |
| 0495 | 20 | | GA | | 2-11 | 27-61-15 | D00667C | 5 | | | GD01844 | DC.. | 2 | | ALL |
| 0496 | 22 | | GA | | 0-7 | 27-61-15 | D00667A | A08 | | | D00667A | C08 | | | ALL |
| 0499 | 22 | | GA | | 0-7 | 27-61-16 | D00669B | C07 | | | D00669B | D06 | | | ALL |
| 0500 | 22 | | GA | | 0-7 | 27-61-16 | D00669B | D03 | | | D00669B | C03 | | | ALL |
| 0501 | 22 | | GA | | 3-0 | 27-61-16 | D00669B | B06 | | | GD01850 | DC.. | 2 | | ALL |
| 0502 | 16 | | GA | | 3-0 | 27-61-16 | D00669C | 10 | | | GD01850 | DC.. | 2 | | ALL |
| 0503 | 16 | | GA | | 3-0 | 27-61-16 | D00669C | 9 | | | GD01850 | DC.. | 2 | | ALL |
| 0504 | 20 | | GA | | 3-0 | 27-61-16 | D00669C | 6 | | | GD01850 | DC.. | 2 | | ALL |
| 0505 | 20 | | GA | | 3-0 | 27-61-16 | D00669C | 5 | | | GD01850 | DC.. | 2 | | ALL |
| 0506 | 20 | | GA | | 2-11 | 22-21-21 | D00351C | 1 | | | GD01848 | ST.. | 2 | | ALL |
| 0507 | 20 | | GA | | 2-11 | 22-21-21 | D00351C | 4 | | | GD01848 | ST.. | 2 | | ALL |
| 0508 | 20 | | GA | | 2-11 | 22-21-21 | D00351C | 6 | | | GD01848 | ST.. | 2 | | ALL |
| 0509 | 16 | | GA | | 2-11 | 22-21-21 | D00351C | 8 | | | GD01848 | ST.. | 2 | | ALL |
| 0510 | 16 | | GA | | 2-11 | 22-21-21 | D00351C | 2 | | | GD01848 | DC.. | 2 | | ALL |
| 0511 | 16 | | GA | | 2-11 | 22-21-21 | D00351C | 3 | | | GD01848 | DC.. | 2 | | ALL |
| 0512 | 16 | | GA | | 2-11 | 22-21-21 | D00351C | 9 | | | GD01848 | DC.. | 2 | | ALL |
| 0513 | 16 | | GA | | 2-11 | 22-21-21 | D00351C | 10 | | | GD01848 | DC.. | 2 | | ALL |
| 0514 | 22 | | GA | | 3-1 | 27-21-22 | D00711B | D15 | | | GD01842 | DC.. | 2 | | ALL |
| 0579 | 22 | | GA | | 2-0 | 27-09-13 | D00675B | F06 | | | TB0108Y | A089 | BJ | | ALL |
| 0580 | 22 | | GA | | 2-0 | 27-09-13 | D00675B | F05 | | | TB0108Y | C089 | BJ | | ALL |
| 0581 | 22 | | GA | | 2-6 | 27-09-13 | D41781J | 5 | | | TB0108Y | A089 | BJ | | ALL |
| 0582 | 22 | | GA | | 2-6 | 27-09-13 | D41781J | 6 | | | TB0108Y | C089 | BJ | | ALL |
| 0583 | 22 | | GA | | 2-4 | 27-09-13 | D00351B | A12 | | | TB0108Y | A089 | BJ | | ALL |
| 0584 | 22 | | GA | | 2-4 | 27-09-13 | D00351B | B12 | | | TB0108Y | C089 | BJ | | ALL |
| 0585 | 22 | | GA | | 3-1 | 27-41-21 | D00675B | H11 | | | GD01845 | DC.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 38

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | | 286N1165 | | | | E4-1 SHELF (continued) | | | | | | | | | |
| 0586 | 22 | GA | | | 3-1 | 27-41-21 | D00675B | H13 | | | GD01845 | DC.. | 2 | | ALL |
| 0587 | 22 | GA | | | 3-1 | 27-41-21 | D00675B | H08 | | | GD01845 | DC.. | 2 | | ALL |
| 0588 | 22 | GA | | | 3-1 | 27-41-21 | D00675B | H09 | | | GD01845 | DC.. | 2 | | ALL |
| 0589 | 22 | GA | | | 3-1 | 27-41-21 | D00675C | 3 | | | GD01845 | DC.. | 2 | | ALL |
| 0590 | 22 | GA | | | 3-1 | 27-41-21 | D00675C | 2 | | | GD01845 | DC.. | 2 | | ALL |
| 0591 | 22 | GA | | | 3-1 | 27-41-21 | D00675C | 8 | | | GD01845 | DC.. | 2 | | ALL |
| 0592 | 22 | GA | | | 3-1 | 27-41-21 | D00675C | 7 | | | GD01845 | DC.. | 2 | | ALL |
| 0593 | 22 | GA | | | 3-1 | 27-41-21 | D00675C | 10 | | | GD01845 | DC.. | 2 | | ALL |
| 0594 | 22 | GA | | | 3-1 | 27-41-21 | D00675C | 11 | | | GD01845 | DC.. | 2 | | ALL |
| 0595 | 22 | GA | | | 2-6 | 27-09-12 | D41781J | 10 | | | TB0108Y | A090 | BJ | | ALL |
| 0601 | 22 | GA | | | 2-4 | 27-31-22 | D00675A | A02 | | | D41785J | 7 | | | ALL |
| 0602 | 22 | GA | | | 2-4 | 27-31-22 | D00675A | A03 | | | D41785J | 8 | | | ALL |
| 0603 | 22 | GA | | | 2-4 | 27-31-22 | D00675B | A11 | | | D41785J | 9 | | | ALL |
| 0604 | 22 | GA | | | 3-5 | 27-61-12 | D00669A | E15 | | | D00665A | G15 | | | ALL |
| 0605 | 22 | GA | | | 3-5 | 27-61-12 | D00669A | F15 | | | D00665A | D15 | | | ALL |
| 0606 | 22 | GA | | | 2-10 | 27-61-12 | D00669A | D15 | | | D00667A | F15 | | | ALL |
| 0607 | 22 | GA | | | 2-10 | 27-61-12 | D00669A | G15 | | | D00667A | E15 | | | ALL |
| 0608 | 22 | GA | | | 3-5 | 27-61-12 | D00669A | D14 | | | D00665A | G14 | | | ALL |
| 0609 | 22 | GA | | | 3-5 | 27-61-12 | D00669A | F14 | | | D00665A | E14 | | | ALL |
| 0610 | 22 | GA | | | 2-10 | 27-61-12 | D00669A | E14 | | | D00667A | F14 | | | ALL |
| 0611 | 22 | GA | | | 2-10 | 27-61-12 | D00669A | G14 | | | D00667A | D14 | | | ALL |
| 0612 | 22 | GA | | | 3-5 | 27-61-12 | D00669A | D13 | | | D00665A | G13 | | | ALL |
| 0613 | 22 | GA | | | 3-5 | 27-61-12 | D00669A | F13 | | | D00665A | E13 | | | ALL |
| 0614 | 22 | GA | | | 2-10 | 27-61-12 | D00669A | E13 | | | D00667A | F13 | | | ALL |
| 0615 | 22 | GA | | | 2-10 | 27-61-12 | D00669A | G13 | | | D00667A | D13 | | | ALL |
| 0616 | 22 | GA | | | 2-1 | 27-61-12 | D00667A | G13 | | | D00665A | D13 | | | ALL |
| 0617 | 22 | GA | | | 2-1 | 27-61-12 | D00667A | E13 | | | D00665A | F13 | | | ALL |
| 0618 | 22 | GA | | | 2-1 | 27-61-12 | D00667A | G14 | | | D00665A | D14 | | | ALL |
| 0619 | 22 | GA | | | 2-1 | 27-61-12 | D00667A | E14 | | | D00665A | F14 | | | ALL |
| 0620 | 22 | GA | | | 2-1 | 27-61-12 | D00667A | G15 | | | D00665A | E15 | | | ALL |
| 0621 | 22 | GA | | | 2-1 | 27-61-12 | D00667A | D15 | | | D00665A | F15 | | | ALL |
| 0622 | 22 | GA | | | 3-5 | 27-09-14 | D41785J | 17 | | | TB0108Y | A112 | BJ | | ALL |
| 0623 | 22 | GA | | | 3-2 | 27-09-14 | D00671B | K13 | | | TB0108Y | A083 | BJ | | ALL |
| 0624 | 22 | GA | | | 2-2 | 27-09-14 | D00711A | C15 | | | D41785J | 23 | | | ALL |
| 0625 | 22 | GA | | | 2-9 | 27-09-14 | D00351B | G10 | | | D41785J | 18 | | | ALL |
| 0626 | 22 | GA | | | 2-4 | 27-09-14 | D00675B | A15 | | | D41785J | 24 | | | ALL |
| 0627 | 22 | GA | | | 1-10 | 27-09-14 | D00669A | H14 | | | TB0108Y | A112 | BJ | | ALL |
| 0628 | 22 | GA | | | 3-1 | 27-09-14 | D00667A | H14 | | | TB0108Y | A112 | BJ | | ALL |
| 0629 | 22 | GA | | | 3-7 | 27-09-14 | D00665A | H14 | | | TB0108Y | A112 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 39

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 0630 | 22 | | GA | | 3-0 | 27-09-14 | D00673B | | K13 | | TB0108Y | A083 | BJ | | ALL |
| 0633 | 22 | | GA | | 2-8 | 27-61-12 | D00669A | | H15 | | TB0108Y | C083 | BJ | | ALL |
| 0634 | 22 | | GA | | 3-5 | 27-61-12 | D00665A | | C15 | | D00669A | C14 | | | ALL |
| 0635 | 22 | | GA | | 0-7 | 27-61-12 | D00669C | | 4 | | D00669A | B07 | | | ALL |
| 0636 | 22 | | GA | | 2-7 | 27-61-12 | D41785J | | 10 | | TB0108Y | C083 | BJ | | ALL |
| 0637 | 22 | | GA | | 2-3 | 27-61-12 | D00667A | | H15 | | TB0108Y | C083 | BJ | | ALL |
| 0640 | 22 | | GA | | 2-10 | 27-61-12 | D00669A | | C15 | | D00667A | C14 | | | ALL |
| 0641 | 22 | | GA | | 0-7 | 27-61-12 | D00667C | | 4 | | D00667A | B07 | | | ALL |
| 0642 | 22 | | GA | | 0-7 | 27-61-12 | D00665C | | 4 | | D00665A | B07 | | | ALL |
| 0643 | 22 | | GA | | 2-10 | 27-61-12 | D00665A | | H15 | | TB0108Y | C083 | BJ | | ALL |
| 0644 | 22 | | GA | | 2-7 | 27-09-14 | D41785J | | 13 | | TB0108Y | A083 | BJ | | ALL |
| 0645 | 22 | | GA | | 2-1 | 27-61-12 | D00667A | | C15 | | D00665A | C14 | | | ALL |
| 0647 | 22 | | GA | | 2-9 | 22-21-21 | D41785J | | 11 | | D00351B | K08 | | | ALL |
| 0648 | 22 | | GA | | 2-9 | 22-21-21 | D41785J | | 12 | | D00351B | K07 | | | ALL |
| 0650 | 22 | | GA | | 2-4 | 22-24-21 | D41785J | | 1 | | D00675B | C12 | | | ALL |
| 0651 | 22 | | GA | | 2-4 | 22-22-21 | D00675B | | E05 | | D41785J | 2 | | | ALL |
| 0652 | 22 | | GA | | 2-3 | 27-21-12 | D41773J | | 38 | | D00711A | D12 | | | ALL |
| 0653 | 22 | | GA | | 2-2 | 27-21-12 | D41785J | | 6 | | D00711B | A14 | | | ALL |
| 0654 | 22 | | GA | | 2-4 | 27-41-21 | D00675B | | C11 | | D41785J | 3 | | | ALL |
| 0655 | 22 | | GA | | 2-4 | 27-41-21 | D00675B | | C13 | | D41785J | 4 | | | ALL |
| 0700 | 22 | | GA | | 2-1 | 27-41-21 | D00675B | | G08 | | GD01849 | DC.. | 2 | | ALL |
| 0701 | 22 | | GA | | 2-1 | 27-41-21 | D00675B | | G09 | | GD01849 | DC.. | 2 | | ALL |
| 0702 | 22 | | GA | | 2-1 | 27-41-21 | D00675B | | G10 | | GD01849 | DC.. | 2 | | ALL |
| 0703 | 22 | | GA | | 2-1 | 27-41-21 | D00675B | | G11 | | GD01849 | DC.. | 2 | | ALL |
| 0704 | 22 | | GA | | 2-1 | 27-41-21 | D00675B | | G12 | | GD01849 | DC.. | 2 | | ALL |
| 0705 | 22 | | GA | | 2-1 | 27-41-21 | D00675B | | G13 | | GD01849 | DC.. | 2 | | ALL |
| 0706 | 22 | | GA | | 2-1 | 27-41-21 | D00675B | | G14 | | GD01849 | DC.. | 2 | | ALL |
| 0707 | 22 | | GA | | 2-1 | 27-41-21 | D00675B | | G15 | | GD01849 | DC.. | 2 | | ALL |
| 2004B | 22 | | GB | BY | 2-9 | 27-61-14 | D00665A | | G08 | | D41767J | 3 | | | 001-099 |
| 2004B | 22 | | GB | BY | 2-1 | 27-61-14 | D00665A | | G08 | | D41767J | 3 | | | 115-199 |
| 2004R | 22 | | GB | BY | 0-0 | 27-61-14 | D00665A | | G09 | | D41767J | 1 | | | ALL |
| 2005B | 22 | | GB | BZ | 2-9 | 27-61-14 | D00665A | | K09 | | D41767J | 5 | | | 001-099 |
| 2005B | 22 | | GB | BZ | 2-1 | 27-61-14 | D00665A | | K09 | | D41767J | 5 | | | 115-199 |
| 2005R | 22 | | GB | BZ | 0-0 | 27-61-14 | D00665A | | K08 | | D41767J | 7 | | | ALL |
| 2006B | 22 | | GB | CB | 2-9 | 27-61-14 | D00665A | | J11 | | TB0108Y | A002 | BJ | | ALL |
| 2006R | 22 | | GB | CB | 0-0 | 27-61-14 | D00665A | | K11 | | TB0108Y | C001 | BJ | | ALL |
| 2007B | 22 | | GB | CE | 2-5 | 27-61-14 | D41767J | | 8 | | TB0108Y | A002 | BJ | | 001-099 |
| 2007B | 22 | | GB | CE | 3-3 | 27-61-14 | D41767J | | 8 | | TB0108Y | A002 | BJ | | 115-199 |
| 2007R | 22 | | GB | CE | 0-0 | 27-61-14 | D41767J | | 9 | | TB0108Y | C001 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 40

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 2008B | 22 | GB | CF | | 2-5 | 27-61-14 | D41767J | 18 | | | TB0108Y | A002 | BJ | | 001-099 |
| 2008B | 22 | GB | CF | | 3-3 | 27-61-14 | D41767J | 18 | | | TB0108Y | A002 | BJ | | 115-199 |
| 2008R | 22 | GB | CF | | 0-0 | 27-61-14 | D41767J | 19 | | | TB0108Y | C001 | BJ | | ALL |
| 2009B | 22 | GB | BX | | 2-9 | 27-61-14 | D00665A | J09 | | | D41767J | 15 | | | 001-099 |
| 2009B | 22 | GB | BX | | 2-1 | 27-61-14 | D00665A | J09 | | | D41767J | 15 | | | 115-199 |
| 2009R | 22 | GB | BX | | 0-0 | 27-61-14 | D00665A | J08 | | | D41767J | 17 | | | ALL |
| 2010B | 22 | GB | CA | | 2-9 | 27-61-14 | D00665A | G11 | | | D41767J | 13 | | | 001-099 |
| 2010B | 22 | GB | CA | | 2-1 | 27-61-14 | D00665A | G11 | | | D41767J | 13 | | | 115-199 |
| 2010R | 22 | GB | CA | | 0-0 | 27-61-14 | D00665A | G10 | | | D41767J | 11 | | | ALL |
| 2011B | 22 | GB | CC | | 2-9 | 27-61-14 | D00665A | J04 | | | TB0108Y | A003 | BJ | | ALL |
| 2011R | 22 | GB | CC | | 0-0 | 27-61-14 | D00665A | J03 | | | TB0108Y | C002 | BJ | | ALL |
| 2012B | 22 | GB | CD | | 2-9 | 27-61-14 | D00665A | K04 | | | TB0108Y | A004 | BJ | | ALL |
| 2012R | 22 | GB | CD | | 0-0 | 27-61-14 | D00665A | K03 | | | TB0108Y | C003 | BJ | | ALL |
| 2013B | 22 | GB | AL | | 2-9 | 27-61-14 | D00665A | J06 | | | TB0108Z | 6 | BJ | | ALL |
| 2013R | 22 | GB | AL | | 0-0 | 27-61-14 | D00665A | K06 | | | TB0108Z | 5 | BJ | | ALL |
| 2014B | 22 | GB | AD | | 2-5 | 27-61-15 | D41767J | 22 | | | TB0108Y | A003 | BJ | | 001-099 |
| 2014B | 22 | GB | AD | | 3-3 | 27-61-15 | D41767J | 31 | | | TB0108Y | A003 | BJ | | 115-199 |
| 2014R | 22 | GB | AD | | 0-0 | 27-61-15 | D41767J | 21 | | | TB0108Y | C002 | BJ | | 001-099 |
| 2014R | 22 | GB | AD | | 0-0 | 27-61-15 | D41767J | 32 | | | TB0108Y | C002 | BJ | | 115-199 |
| 2015B | 22 | GB | AE | | 2-5 | 27-61-15 | D41767J | 24 | | | TB0108Z | 6 | BJ | | 001-099 |
| 2015B | 22 | GB | AE | | 3-3 | 27-61-15 | D41767J | 34 | | | TB0108Z | 6 | BJ | | 115-199 |
| 2015R | 22 | GB | AE | | 0-0 | 27-61-15 | D41767J | 23 | | | TB0108Z | 5 | BJ | | 001-099 |
| 2015R | 22 | GB | AE | | 0-0 | 27-61-15 | D41767J | 33 | | | TB0108Z | 5 | BJ | | 115-199 |
| 2016B | 22 | GB | AF | | 2-5 | 27-61-15 | D41767J | 26 | | | TB0108Z | 6 | BJ | | 001-099 |
| 2016B | 22 | GB | AF | | 3-3 | 27-61-15 | D41767J | 36 | | | TB0108Z | 6 | BJ | | 115-199 |
| 2016R | 22 | GB | AF | | 0-0 | 27-61-15 | D41767J | 25 | | | TB0108Z | 5 | BJ | | 001-099 |
| 2016R | 22 | GB | AF | | 0-0 | 27-61-15 | D41767J | 35 | | | TB0108Z | 5 | BJ | | 115-199 |
| 2017B | 22 | GB | AG | | 2-5 | 27-61-15 | D41767J | 28 | | | TB0108Y | A004 | BJ | | 001-099 |
| 2017B | 22 | GB | AG | | 3-3 | 27-61-15 | D41767J | 38 | | | TB0108Y | A004 | BJ | | 115-199 |
| 2017R | 22 | GB | AG | | 0-0 | 27-61-15 | D41767J | 27 | | | TB0108Y | C003 | BJ | | 001-099 |
| 2017R | 22 | GB | AG | | 0-0 | 27-61-15 | D41767J | 37 | | | TB0108Y | C003 | BJ | | 115-199 |
| 2018B | 22 | GB | AH | | 3-3 | 27-61-15 | D00667B | J05 | | | TB0108Y | A003 | BJ | | ALL |
| 2018R | 22 | GB | AH | | 0-0 | 27-61-15 | D00667B | J04 | | | TB0108Y | C002 | BJ | | ALL |
| 2019B | 22 | GB | BV | | 3-3 | 27-61-15 | D00667B | K05 | | | TB0108Y | A004 | BJ | | ALL |
| 2019R | 22 | GB | BV | | 0-0 | 27-61-15 | D00667B | K04 | | | TB0108Y | C003 | BJ | | ALL |
| 2020B | 22 | GB | AW | | 2-5 | 27-61-15 | TB0108Z | 6 | BJ | | D00671A | C01 | | | ALL |
| 2020R | 22 | GB | AW | | 0-0 | 27-61-15 | TB0108Z | 5 | BJ | | D00671A | A01 | | | ALL |
| 2021B | 22 | GB | AV | | 3-3 | 27-61-15 | TB0108Z | 6 | BJ | | D00667B | J07 | | | ALL |
| 2021R | 22 | GB | AV | | 0-0 | 27-61-15 | TB0108Z | 5 | BJ | | D00667B | K07 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 41

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 2022B | 22 | GB | BF | | 4-6 | 27-61-16 | D00669B | J13 | | | TB0108Y | A003 | BJ | | ALL |
| 2022R | 22 | GB | BF | | 0-0 | 27-61-16 | D00669B | J12 | | | TB0108Y | C002 | BJ | | ALL |
| 2023B | 22 | GB | BG | | 4-6 | 27-61-16 | D00669B | K13 | | | TB0108Y | A004 | BJ | | ALL |
| 2023R | 22 | GB | BG | | 0-0 | 27-61-16 | D00669B | K12 | | | TB0108Y | C003 | BJ | | ALL |
| 2024B | 22 | GB | BS | | 4-6 | 27-61-16 | TB0108Z | 6 | BJ | | D00669B | J15 | | | ALL |
| 2024R | 22 | GB | BS | | 0-0 | 27-61-16 | TB0108Z | 5 | BJ | | D00669B | K15 | | | ALL |
| 2025B | 22 | GB | CT | | 2-0 | 22-21-21 | D00351A | D15 | | | D41793J | 9 | | | ALL |
| 2025R | 22 | GB | CT | | 0-0 | 22-21-21 | D00351A | E14 | | | D41793J | 8 | | | ALL |
| 2026B | 22 | GB | CV | | 4-1 | 22-21-21 | D00351A | E15 | | | TB0108Z | 14 | BJ | | ALL |
| 2026R | 22 | GB | CV | | 0-0 | 22-21-21 | D00351A | F14 | | | TB0108Z | 13 | BJ | | ALL |
| 2027B | 22 | GB | CW | | 3-11 | 22-21-21 | D41793J | 14 | | | TB0108Z | 14 | BJ | | ALL |
| 2027R | 22 | GB | CW | | 0-0 | 22-21-21 | D41793J | 13 | | | TB0108Z | 13 | BJ | | ALL |
| 2028B | 22 | GB | CX | | 2-4 | 27-21-22 | D00671A | C12 | | | TB0108Z | 14 | BJ | | ALL |
| 2028R | 22 | GB | CX | | 0-0 | 27-21-22 | D00671A | A12 | | | TB0108Z | 13 | BJ | | ALL |
| 2029B | 22 | GB | CY | | 3-11 | 27-21-22 | D41793J | 2 | | | TB0108Z | 14 | BJ | | ALL |
| 2029R | 22 | GB | CY | | 0-0 | 27-21-22 | D41793J | 1 | | | TB0108Z | 13 | BJ | | ALL |
| 2030B | 22 | GB | CZ | | 2-11 | 27-21-22 | D00711A | A10 | | | TB0108Z | 14 | BJ | | ALL |
| 2030R | 22 | GB | CZ | | 0-0 | 27-21-22 | D00711A | A09 | | | TB0108Z | 13 | BJ | | ALL |
| 2031B | 22 | GB | DA | | 3-0 | 27-21-22 | D00711B | A10 | | | TB0108Y | C012 | BJ | | ALL |
| 2031R | 22 | GB | DA | | 0-0 | 27-21-22 | D00711B | A09 | | | TB0108Y | A012 | BJ | | ALL |
| 2032B | 22 | GB | DB | | 4-0 | 27-21-22 | D41793J | 7 | | | TB0108Y | C012 | BJ | | ALL |
| 2032R | 22 | GB | DB | | 0-0 | 27-21-22 | D41793J | 6 | | | TB0108Y | A012 | BJ | | ALL |
| 2033B | 22 | GB | DE | | 3-8 | 27-21-22 | D41773J | 24 | | | TB0108Y | C012 | BJ | | ALL |
| 2033R | 22 | GB | DE | | 0-0 | 27-21-22 | D41773J | 23 | | | TB0108Y | A012 | BJ | | ALL |
| 2035B | 22 | GB | DK | | 2-3 | 27-21-22 | D00675A | K05 | | | D00711A | D04 | | | ALL |
| 2035R | 22 | GB | DK | | 0-0 | 27-21-22 | D00675A | K04 | | | D00711A | D05 | | | ALL |
| 2036B | 22 | GB | DC | | 4-1 | 27-09-11 | D00671B | C10 | | | D00673B | A10 | | | ALL |
| 2036R | 22 | GB | DC | | 0-0 | 27-09-11 | D00671B | A10 | | | D00673B | C10 | | | ALL |
| 2101B | 22 | GB | CH | | 3-0 | 27-61-14 | D41771J | 22 | | | TB0108Y | A043 | BJ | | ALL |
| 2101R | 22 | GB | CH | | 0-0 | 27-61-14 | D41771J | 21 | | | TB0108Y | C042 | BJ | | ALL |
| 2102B | 22 | GB | CM | | 1-10 | 27-61-14 | D00665B | J05 | | | TB0108Y | A043 | BJ | | ALL |
| 2102R | 22 | GB | CM | | 0-0 | 27-61-14 | D00665B | J04 | | | TB0108Y | C042 | BJ | | ALL |
| 2103B | 22 | GB | CJ | | 3-0 | 27-61-14 | D41771J | 24 | | | TB0108Z | 46 | BJ | | ALL |
| 2103R | 22 | GB | CJ | | 0-0 | 27-61-14 | D41771J | 23 | | | TB0108Z | 45 | BJ | | ALL |
| 2104B | 22 | GB | CK | | 3-0 | 27-61-14 | D41771J | 26 | | | TB0108Z | 46 | BJ | | ALL |
| 2104R | 22 | GB | CK | | 0-0 | 27-61-14 | D41771J | 25 | | | TB0108Z | 45 | BJ | | ALL |
| 2105B | 22 | GB | CL | | 3-0 | 27-61-14 | D41771J | 28 | | | TB0108Y | A044 | BJ | | ALL |
| 2105R | 22 | GB | CL | | 0-0 | 27-61-14 | D41771J | 27 | | | TB0108Y | C043 | BJ | | ALL |
| 2106B | 22 | GB | CN | | 1-10 | 27-61-14 | D00665B | K05 | | | TB0108Y | A044 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 42

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | | 286N1165 | | | | E4-1 SHELF (continued) | | | | | | | | | |
| 2106R | 22 | GB | CN | | 0-0 | 27-61-14 | D00665B | K04 | | | TB0108Y | C043 | BJ | | ALL |
| 2107B | 22 | GB | AA | | 2-3 | 27-61-14 | D00671B | C01 | | | TB0108Z | 46 | BJ | | ALL |
| 2107R | 22 | GB | AA | | 0-0 | 27-61-14 | D00671B | A01 | | | TB0108Z | 45 | BJ | | ALL |
| 2108B | 22 | GB | AB | | 1-10 | 27-61-14 | D00665B | J07 | | | TB0108Z | 46 | BJ | | ALL |
| 2108R | 22 | GB | AB | | 0-0 | 27-61-14 | D00665B | K07 | | | TB0108Z | 45 | BJ | | ALL |
| 2109B | 22 | GB | AJ | | 2-1 | 27-61-15 | D00667B | J13 | | | TB0108Y | A043 | BJ | | ALL |
| 2109R | 22 | GB | AJ | | 0-0 | 27-61-15 | D00667B | J12 | | | TB0108Y | C042 | BJ | | ALL |
| 2110B | 22 | GB | AK | | 2-1 | 27-61-15 | D00667B | K13 | | | TB0108Y | A044 | BJ | | ALL |
| 2110R | 22 | GB | AK | | 0-0 | 27-61-15 | D00667B | K12 | | | TB0108Y | C043 | BJ | | ALL |
| 2111B | 22 | GB | AY | | 2-1 | 27-61-15 | TB0108Z | 46 | BJ | | D00667B | J15 | | | ALL |
| 2111R | 22 | GB | AY | | 0-0 | 27-61-15 | TB0108Z | 45 | BJ | | D00667B | K15 | | | ALL |
| 2112B | 22 | GB | BH | | 2-7 | 27-61-16 | D00669A | G08 | | | D41771J | 3 | | | ALL |
| 2112R | 22 | GB | BH | | 0-0 | 27-61-16 | D00669A | G09 | | | D41771J | 1 | | | ALL |
| 2113B | 22 | GB | BJ | | 2-7 | 27-61-16 | D00669A | K09 | | | D41771J | 5 | | | ALL |
| 2113R | 22 | GB | BJ | | 0-0 | 27-61-16 | D00669A | K08 | | | D41771J | 7 | | | ALL |
| 2114B | 22 | GB | BM | | 3-4 | 27-61-16 | D00669A | J11 | | | TB0108Y | C041 | BJ | | ALL |
| 2114R | 22 | GB | BM | | 0-0 | 27-61-16 | D00669A | K11 | | | TB0108Y | A041 | BJ | | ALL |
| 2115B | 22 | GB | BK | | 2-7 | 27-61-16 | D00669A | J09 | | | D41771J | 15 | | | ALL |
| 2115R | 22 | GB | BK | | 0-0 | 27-61-16 | D00669A | J08 | | | D41771J | 17 | | | ALL |
| 2116B | 22 | GB | BL | | 2-7 | 27-61-16 | D00669A | G11 | | | D41771J | 13 | | | ALL |
| 2116R | 22 | GB | BL | | 0-0 | 27-61-16 | D00669A | G10 | | | D41771J | 11 | | | ALL |
| 2117B | 22 | GB | BN | | 3-4 | 27-61-16 | D00669A | J04 | | | TB0108Y | A043 | BJ | | ALL |
| 2117R | 22 | GB | BN | | 0-0 | 27-61-16 | D00669A | J03 | | | TB0108Y | C042 | BJ | | ALL |
| 2118B | 22 | GB | CG | | 3-4 | 27-61-16 | D00669A | K04 | | | TB0108Y | A044 | BJ | | ALL |
| 2118R | 22 | GB | CG | | 0-0 | 27-61-16 | D00669A | K03 | | | TB0108Y | C043 | BJ | | ALL |
| 2119B | 22 | GB | BP | | 3-0 | 27-61-16 | D41771J | 8 | | | TB0108Y | C041 | BJ | | ALL |
| 2119R | 22 | GB | BP | | 0-0 | 27-61-16 | D41771J | 9 | | | TB0108Y | A041 | BJ | | ALL |
| 2120B | 22 | GB | BQ | | 3-0 | 27-61-16 | D41771J | 18 | | | TB0108Y | C041 | BJ | | ALL |
| 2120R | 22 | GB | BQ | | 0-0 | 27-61-16 | D41771J | 19 | | | TB0108Y | A041 | BJ | | ALL |
| 2121B | 22 | GB | BT | | 3-4 | 27-61-16 | TB0108Z | 46 | BJ | | D00669A | J06 | | | ALL |
| 2121R | 22 | GB | BT | | 0-0 | 27-61-16 | TB0108Z | 45 | BJ | | D00669A | K06 | | | ALL |
| 2122B | 22 | GB | DF | | 2-3 | 27-21-22 | D00675A | K14 | | | D00711B | D10 | | | ALL |
| 2122R | 22 | GB | DF | | 0-0 | 27-21-22 | D00675A | K13 | | | D00711B | D09 | | | ALL |
| 2123B | 22 | GB | DW | | 2-0 | 22-24-21 | D41367J | 24 | | | D00675A | E10 | | | ALL |
| 2123R | 22 | GB | DW | | 0-0 | 22-24-21 | D41367J | 23 | | | D00675A | E09 | | | ALL |
| 2124B | 22 | GB | ED | | 2-2 | 27-21-12 | D41777J | 16 | | | D00711A | A04 | | | ALL |
| 2124R | 22 | GB | ED | | 0-0 | 27-21-12 | D41777J | 15 | | | D00711A | A05 | | | ALL |
| 2125B | 22 | GB | EC | | 2-11 | 27-21-22 | TB0108Z | 14 | BJ | | D00711B | A05 | | | ALL |
| 2125R | 22 | GB | EC | | 0-0 | 27-21-22 | TB0108Z | 13 | BJ | | D00711B | A04 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 43

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 2201B | 22 | GB | CP | | 2-10 | 27-61-14 | D00665B | J13 | | | TB0108Y | C082 | BJ | | ALL |
| 2201R | 22 | GB | CP | | 0-0 | 27-61-14 | D00665B | J12 | | | TB0108Y | A082 | BJ | | ALL |
| 2202B | 22 | GB | CQ | | 2-10 | 27-61-14 | D00665B | K13 | | | TB0108Y | C084 | BJ | | ALL |
| 2202R | 22 | GB | CQ | | 0-0 | 27-61-14 | D00665B | K12 | | | TB0108Y | A084 | BJ | | ALL |
| 2203B | 22 | GB | AC | | 2-10 | 27-61-14 | D00665B | J15 | | | TB0108Z | 86 | BJ | | ALL |
| 2203R | 22 | GB | AC | | 0-0 | 27-61-14 | D00665B | K15 | | | TB0108Z | 85 | BJ | | ALL |
| 2204B | 22 | GB | AM | | 2-1 | 27-61-15 | D00667A | G08 | | | D41769J | 3 | | | ALL |
| 2204R | 22 | GB | AM | | 0-0 | 27-61-15 | D00667A | G09 | | | D41769J | 1 | | | ALL |
| 2205B | 22 | GB | AN | | 2-1 | 27-61-15 | D00667A | K09 | | | D41769J | 5 | | | ALL |
| 2205R | 22 | GB | AN | | 0-0 | 27-61-15 | D00667A | K08 | | | D41769J | 7 | | | ALL |
| 2206B | 22 | GB | AP | | 2-3 | 27-61-15 | D00667A | J11 | | | TB0108Y | C081 | BJ | | ALL |
| 2206R | 22 | GB | AP | | 0-0 | 27-61-15 | D00667A | K11 | | | TB0108Y | A081 | BJ | | ALL |
| 2207B | 22 | GB | AQ | | 2-1 | 27-61-15 | D00667A | J09 | | | D41769J | 15 | | | ALL |
| 2207R | 22 | GB | AQ | | 0-0 | 27-61-15 | D00667A | J08 | | | D41769J | 17 | | | ALL |
| 2208B | 22 | GB | AR | | 2-1 | 27-61-15 | D00667A | G11 | | | D41769J | 13 | | | ALL |
| 2208R | 22 | GB | AR | | 0-0 | 27-61-15 | D00667A | G10 | | | D41769J | 11 | | | ALL |
| 2209B | 22 | GB | BW | | 2-3 | 27-61-15 | D00667A | J04 | | | TB0108Y | C082 | BJ | | ALL |
| 2209R | 22 | GB | BW | | 0-0 | 27-61-15 | D00667A | J03 | | | TB0108Y | A082 | BJ | | ALL |
| 2210B | 22 | GB | AS | | 2-3 | 27-61-15 | D00667A | K04 | | | TB0108Y | C084 | BJ | | ALL |
| 2210R | 22 | GB | AS | | 0-0 | 27-61-15 | D00667A | K03 | | | TB0108Y | A084 | BJ | | ALL |
| 2211B | 22 | GB | AT | | 2-9 | 27-61-15 | D41769J | 8 | | | TB0108Y | C081 | BJ | | ALL |
| 2211R | 22 | GB | AT | | 0-0 | 27-61-15 | D41769J | 9 | | | TB0108Y | A081 | BJ | | ALL |
| 2212B | 22 | GB | AU | | 2-9 | 27-61-15 | D41769J | 18 | | | TB0108Y | C081 | BJ | | ALL |
| 2212R | 22 | GB | AU | | 0-0 | 27-61-15 | D41769J | 19 | | | TB0108Y | A081 | BJ | | ALL |
| 2213B | 22 | GB | AX | | 2-4 | 27-61-15 | TB0108Z | 86 | BJ | | D00667A | J06 | | | ALL |
| 2213R | 22 | GB | AX | | 0-0 | 27-61-15 | TB0108Z | 85 | BJ | | D00667A | K06 | | | ALL |
| 2214B | 22 | GB | AZ | | 2-9 | 27-61-16 | D41769J | 22 | | | TB0108Y | C082 | BJ | | 001-099 |
| 2214B | 22 | GB | AZ | | 2-9 | 27-61-16 | D41769J | 31 | | | TB0108Y | C082 | BJ | | 115-199 |
| 2214R | 22 | GB | AZ | | 0-0 | 27-61-16 | D41769J | 21 | | | TB0108Y | A082 | BJ | | 001-099 |
| 2214R | 22 | GB | AZ | | 0-0 | 27-61-16 | D41769J | 32 | | | TB0108Y | A082 | BJ | | 115-199 |
| 2215B | 22 | GB | BA | | 2-9 | 27-61-16 | D41769J | 24 | | | TB0108Z | 86 | BJ | | 001-099 |
| 2215B | 22 | GB | BA | | 2-9 | 27-61-16 | D41769J | 34 | | | TB0108Z | 86 | BJ | | 115-199 |
| 2215R | 22 | GB | BA | | 0-0 | 27-61-16 | D41769J | 23 | | | TB0108Z | 85 | BJ | | 001-099 |
| 2215R | 22 | GB | BA | | 0-0 | 27-61-16 | D41769J | 33 | | | TB0108Z | 85 | BJ | | 115-199 |
| 2216B | 22 | GB | BB | | 2-9 | 27-61-16 | D41769J | 26 | | | TB0108Z | 86 | BJ | | 001-099 |
| 2216B | 22 | GB | BB | | 2-9 | 27-61-16 | D41769J | 36 | | | TB0108Z | 86 | BJ | | 115-199 |
| 2216R | 22 | GB | BB | | 0-0 | 27-61-16 | D41769J | 25 | | | TB0108Z | 85 | BJ | | 001-099 |
| 2216R | 22 | GB | BB | | 0-0 | 27-61-16 | D41769J | 35 | | | TB0108Z | 85 | BJ | | 115-199 |
| 2217B | 22 | GB | BC | | 2-9 | 27-61-16 | D41769J | 28 | | | TB0108Y | C084 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 44

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|------------|-------------|----|-------|------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | | |
| 2217B | 22 | GB | BC | | 2-9 | 27-61-16 | D41769J | 38 | | | | TB0108Y | C084 | BJ | | 115-199 |
| 2217R | 22 | GB | BC | | 0-0 | 27-61-16 | D41769J | 27 | | | | TB0108Y | A084 | BJ | | 001-099 |
| 2217R | 22 | GB | BC | | 0-0 | 27-61-16 | D41769J | 37 | | | | TB0108Y | A084 | BJ | | 115-199 |
| 2218B | 22 | GB | BD | | 2-8 | 27-61-16 | D00669B | J05 | | | | TB0108Y | C082 | BJ | | ALL |
| 2218R | 22 | GB | BD | | 0-0 | 27-61-16 | D00669B | J04 | | | | TB0108Y | A082 | BJ | | ALL |
| 2219B | 22 | GB | BE | | 2-8 | 27-61-16 | D00669B | K05 | | | | TB0108Y | C084 | BJ | | ALL |
| 2219R | 22 | GB | BE | | 0-0 | 27-61-16 | D00669B | K04 | | | | TB0108Y | A084 | BJ | | ALL |
| 2220B | 22 | GB | BR | | 3-2 | 27-61-16 | D00671B | C05 | | | | TB0108Z | 86 | BJ | | ALL |
| 2220R | 22 | GB | BR | | 0-0 | 27-61-16 | D00671B | A05 | | | | TB0108Z | 85 | BJ | | ALL |
| 2221B | 22 | GB | BU | | 2-8 | 27-61-16 | D00669B | J07 | | | | TB0108Z | 86 | BJ | | ALL |
| 2221R | 22 | GB | BU | | 0-0 | 27-61-16 | D00669B | K07 | | | | TB0108Z | 85 | BJ | | ALL |
| 2222B | 22 | GB | EV | | 2-4 | 22-21-21 | D00351A | H12 | | | | D41791J | 1 | | | ALL |
| 2222R | 22 | GB | EV | | 0-0 | 22-21-21 | D00351A | K12 | | | | D41791J | 2 | | | ALL |
| 2501B | 22 | GU | EW | | 2-4 | 22-21-21 | D00351B | K15 | | | | D41791J | 5 | | | ALL |
| 2501R | 22 | GU | EW | | 0-0 | 22-21-21 | D00351B | K14 | | | | D41791J | 4 | | | ALL |
| 2501Z | | | EW | | 0-0 | 22-21-21 | GD01851 | ST.. | 2 | | | D41791J | 7 | | | ALL |
| 3001B | 22 | GC | CU | | 2-0 | 22-21-21 | D00351A | C14 | | | | D41793J | 11 | | | ALL |
| 3001R | 22 | GC | CU | | 0-0 | 22-21-21 | D00351A | D14 | | | | D41793J | 10 | | | ALL |
| 3001Y | 22 | GC | CU | | 0-0 | 22-21-21 | D00351A | C15 | | | | D41793J | 12 | | | ALL |
| 3002B | 22 | GC | DG | | 2-11 | 27-21-22 | D00711A | B09 | | | | TB0108Y | C015 | BJ | | ALL |
| 3002R | 22 | GC | DG | | 0-0 | 27-21-22 | D00711A | B08 | | | | TB0108Y | A015 | BJ | | ALL |
| 3002Y | 22 | GC | DG | | 0-0 | 27-21-22 | D00711A | B10 | | | | TB0108Y | A016 | BJ | | ALL |
| 3004B | 22 | GC | DJ | | 3-11 | 27-21-22 | D41793J | 4 | | | | TB0108Y | C015 | BJ | | ALL |
| 3004R | 22 | GC | DJ | | 0-0 | 27-21-22 | D41793J | 3 | | | | TB0108Y | A015 | BJ | | ALL |
| 3004Y | 22 | GC | DJ | | 0-0 | 27-21-22 | D41793J | 5 | | | | TB0108Y | A016 | BJ | | ALL |
| 3005B | 22 | GC | EE | | 3-4 | 22-21-21 | D00351A | K02 | | | | D00671A | K06 | | | ALL |
| 3005R | 22 | GC | EE | | 0-0 | 22-21-21 | D00351A | K01 | | | | D00671A | K05 | | | ALL |
| 3005Y | 22 | GC | EE | | 0-0 | 22-21-21 | D00351A | J01 | | | | D00671A | J05 | | | ALL |
| 3006B | 22 | GC | EF | | 3-4 | 22-21-21 | D00351A | H01 | | | | D00671A | J06 | | | ALL |
| 3006R | 22 | GC | EF | | 0-0 | 22-21-21 | D00351A | J02 | | | | D00671A | K07 | | | ALL |
| 3006Y | 22 | GC | EF | | 0-0 | 22-21-21 | D00351A | H02 | | | | D00671A | J07 | | | ALL |
| 3007B | 22 | GC | EG | | 2-4 | 22-21-21 | D00351A | G02 | | | | D00673A | K06 | | | ALL |
| 3007R | 22 | GC | EG | | 0-0 | 22-21-21 | D00351A | G01 | | | | D00673A | K05 | | | ALL |
| 3007Y | 22 | GC | EG | | 0-0 | 22-21-21 | D00351A | F01 | | | | D00673A | J05 | | | ALL |
| 3008B | 22 | GC | EH | | 2-4 | 22-21-21 | D00351A | E01 | | | | D00673A | J06 | | | ALL |
| 3008R | 22 | GC | EH | | 0-0 | 22-21-21 | D00351A | F02 | | | | D00673A | K07 | | | ALL |
| 3008Y | 22 | GC | EH | | 0-0 | 22-21-21 | D00351A | E02 | | | | D00673A | J07 | | | ALL |
| 3009B | 22 | GC | EM | | 2-10 | 27-41-21 | D00671A | H06 | | | | D00675A | H05 | | | ALL |
| 3009R | 22 | GC | EM | | 0-0 | 27-41-21 | D00671A | H05 | | | | D00675A | H04 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 45

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 3009Y | 22 | GC | EM | | 0-0 | 27-41-21 | D00671A | G05 | | | D00675A | H06 | | | ALL |
| 3010B | 22 | GC | EN | | 2-10 | 27-41-21 | D00671A | G06 | | | D00675A | J05 | | | ALL |
| 3010R | 22 | GC | EN | | 0-0 | 27-41-21 | D00671A | H07 | | | D00675A | J04 | | | ALL |
| 3010Y | 22 | GC | EN | | 0-0 | 27-41-21 | D00671A | G07 | | | D00675A | J06 | | | ALL |
| 3011B | 22 | GC | ER | | 2-10 | 27-41-21 | D00673A | H06 | | | D00675A | F05 | | | ALL |
| 3011R | 22 | GC | ER | | 0-0 | 27-41-21 | D00673A | H05 | | | D00675A | F04 | | | ALL |
| 3011Y | 22 | GC | ER | | 0-0 | 27-41-21 | D00673A | G05 | | | D00675A | F06 | | | ALL |
| 3012B | 22 | GC | ES | | 2-10 | 27-41-21 | D00673A | G06 | | | D00675A | G05 | | | ALL |
| 3012R | 22 | GC | ES | | 0-0 | 27-41-21 | D00673A | H07 | | | D00675A | G04 | | | ALL |
| 3012Y | 22 | GC | ES | | 0-0 | 27-41-21 | D00673A | G07 | | | D00675A | G06 | | | ALL |
| 3101B | 22 | GC | EB | | 2-11 | 27-21-22 | TB0108Y | C015 | BJ | | D00711B | B05 | | | ALL |
| 3101R | 22 | GC | EB | | 0-0 | 27-21-22 | TB0108Y | A015 | BJ | | D00711B | B06 | | | ALL |
| 3101Y | 22 | GC | EB | | 0-0 | 27-21-22 | TB0108Y | A016 | BJ | | D00711B | B04 | | | ALL |
| 3102B | 22 | GC | EI | | 3-4 | 22-21-21 | D00351B | K02 | | | D00671A | K09 | | | ALL |
| 3102R | 22 | GC | EI | | 0-0 | 22-21-21 | D00351B | K01 | | | D00671A | K08 | | | ALL |
| 3102Y | 22 | GC | EI | | 0-0 | 22-21-21 | D00351B | J01 | | | D00671A | J08 | | | ALL |
| 3103B | 22 | GC | EJ | | 3-4 | 22-21-21 | D00351B | H01 | | | D00671A | J09 | | | ALL |
| 3103R | 22 | GC | EJ | | 0-0 | 22-21-21 | D00351B | J02 | | | D00671A | K10 | | | ALL |
| 3103Y | 22 | GC | EJ | | 0-0 | 22-21-21 | D00351B | H02 | | | D00671A | J10 | | | ALL |
| 3104B | 22 | GC | EK | | 2-4 | 22-21-21 | D00351B | G02 | | | D00673A | K09 | | | ALL |
| 3104R | 22 | GC | EK | | 0-0 | 22-21-21 | D00351B | G01 | | | D00673A | K08 | | | ALL |
| 3104Y | 22 | GC | EK | | 0-0 | 22-21-21 | D00351B | F01 | | | D00673A | J08 | | | ALL |
| 3105B | 22 | GC | EL | | 2-4 | 22-21-21 | D00351B | E01 | | | D00673A | J09 | | | ALL |
| 3105R | 22 | GC | EL | | 0-0 | 22-21-21 | D00351B | F02 | | | D00673A | K10 | | | ALL |
| 3105Y | 22 | GC | EL | | 0-0 | 22-21-21 | D00351B | E02 | | | D00673A | J10 | | | ALL |
| 3106B | 22 | GC | EP | | 2-10 | 27-41-21 | D00671A | H09 | | | D00675B | K03 | | | ALL |
| 3106R | 22 | GC | EP | | 0-0 | 27-41-21 | D00671A | H08 | | | D00675B | K02 | | | ALL |
| 3106Y | 22 | GC | EP | | 0-0 | 27-41-21 | D00671A | G08 | | | D00675B | K04 | | | ALL |
| 3107B | 22 | GC | EQ | | 2-10 | 27-41-21 | D00671A | G09 | | | D00675B | J03 | | | ALL |
| 3107R | 22 | GC | EQ | | 0-0 | 27-41-21 | D00671A | H10 | | | D00675B | J02 | | | ALL |
| 3107Y | 22 | GC | EQ | | 0-0 | 27-41-21 | D00671A | G10 | | | D00675B | J04 | | | ALL |
| 3108B | 22 | GC | ET | | 2-10 | 27-41-21 | D00673A | H09 | | | D00675B | H03 | | | ALL |
| 3108R | 22 | GC | ET | | 0-0 | 27-41-21 | D00673A | H08 | | | D00675B | H02 | | | ALL |
| 3108Y | 22 | GC | ET | | 0-0 | 27-41-21 | D00673A | G08 | | | D00675B | H04 | | | ALL |
| 3109B | 22 | GC | EU | | 2-10 | 27-41-21 | D00673A | G09 | | | D00675B | G03 | | | ALL |
| 3109R | 22 | GC | EU | | 0-0 | 27-41-21 | D00673A | H10 | | | D00675B | G02 | | | ALL |
| 3109Y | 22 | GC | EU | | 0-0 | 27-41-21 | D00673A | G10 | | | D00675B | G04 | | | ALL |
| 5001B | 24 | G2 | CR | | 4-1 | 22-21-21 | D00351A | A15 | | | TB0108Y | C011 | BJ | | ALL |
| 5001R | 24 | G2 | CR | | 0-0 | 22-21-21 | D00351A | A14 | | | TB0108Y | A011 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 46

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1165 | 286N1165 | | | E4-1 SHELF (continued) | | | | | | | | | | | |
| 5001Z | | | | CR | 0-0 | 22-21-21 | D00351A | DED | | | TB0108Y | | | AD | ALL |
| 5002B | 24 | G2 | | DL | 2-11 | 22-21-21 | D40015J | 5 | | | D00351A | K05 | | | ALL |
| 5002R | 24 | G2 | | DL | 0-0 | 22-21-21 | D40015J | 4 | | | D00351A | K04 | | | ALL |
| 5002Z | | | | DL | 0-0 | 22-21-21 | D40015J | 6 | | | GD01851 | ST.. | 2 | | ALL |
| 5003B | 24 | G2 | | DU | 2-11 | 22-24-21 | D40015J | 2 | | | TB0108Y | C011 | BJ | | ALL |
| 5003R | 24 | G2 | | DU | 0-0 | 22-24-21 | D40015J | 1 | | | TB0108Y | A011 | BJ | | ALL |
| 5003Z | | | | DU | 0-0 | 22-24-21 | D00351A | 3 | | | TB0108Y | | | AD | ALL |
| 5004B | 24 | G2 | | DV | 3-8 | 22-24-21 | D00675A | A12 | | | TB0108Y | C011 | BJ | | ALL |
| 5004R | 24 | G2 | | DV | 0-0 | 22-24-21 | D00675A | A11 | | | TB0108Y | A011 | BJ | | ALL |
| 5004Z | | | | DV | 0-0 | 22-24-21 | D00675A | DED | | | TB0108Y | | | AD | ALL |
| 5101B | 24 | G2 | | CS | 3-0 | 22-21-21 | D00351A | K15 | | | TB0108Y | C055 | BJ | | ALL |
| 5101R | 24 | G2 | | CS | 0-0 | 22-21-21 | D00351A | K14 | | | TB0108Y | A055 | BJ | | ALL |
| 5101Z | | | | CS | 0-0 | 22-21-21 | D00351A | DED | | | TB0108Y | | | AC | ALL |
| 5103B | 24 | G2 | | DQ | 3-0 | 22-21-21 | D00351B | K05 | | | TB0108Y | C053 | BJ | | ALL |
| 5103R | 24 | G2 | | DQ | 0-0 | 22-21-21 | D00351B | K04 | | | TB0108Y | A053 | BJ | | ALL |
| 5103Z | | | | DQ | 0-0 | 22-21-21 | D00351B | DED | | | TB0108Y | | | AB | ALL |
| 5104B | 24 | G2 | | DP | 2-6 | 22-21-21 | D41367J | 11 | | | TB0108Y | C053 | BJ | | ALL |
| 5104R | 24 | G2 | | DP | 0-0 | 22-21-21 | D41367J | 10 | | | TB0108Y | A053 | BJ | | ALL |
| 5104Z | | | | DP | 0-0 | 22-21-21 | D41367J | 12 | | | TB0108Y | | | AB | ALL |
| 5105B | 24 | G2 | | DR | 2-6 | 22-24-21 | D41367J | 20 | | | TB0108Y | C055 | BJ | | ALL |
| 5105R | 24 | G2 | | DR | 0-0 | 22-24-21 | D41367J | 19 | | | TB0108Y | A055 | BJ | | ALL |
| 5105Z | | | | DR | 0-0 | 22-24-21 | D41367J | 21 | | | TB0108Y | | | AC | ALL |
| 5106B | 24 | G2 | | DS | 2-7 | 22-24-21 | D00675A | D12 | | | TB0108Y | C055 | BJ | | ALL |
| 5106R | 24 | G2 | | DS | 0-0 | 22-24-21 | D00675A | D11 | | | TB0108Y | A055 | BJ | | ALL |
| 5106Z | | | | DS | 0-0 | 22-24-21 | D00675A | DED | | | TB0108Y | | | AC | ALL |
| 5108B | 24 | G2 | | DZ | 2-0 | 22-22-21 | D00675A | D08 | | | D41367J | 16 | | | ALL |
| 5108R | 24 | G2 | | DZ | 0-0 | 22-22-21 | D00675A | D07 | | | D41367J | 15 | | | ALL |
| 5108Z | | | | DZ | 0-0 | 22-22-21 | GD01849 | ST.. | 2 | | D41367J | 17 | | | ALL |
| 5201B | 24 | G2 | | DM | 2-3 | 22-21-21 | D41781J | 18 | | | D00351B | A15 | | | ALL |
| 5201R | 24 | G2 | | DM | 0-0 | 22-21-21 | D41781J | 17 | | | D00351B | A14 | | | ALL |
| 5201Z | | | | DM | 0-0 | 22-21-21 | D41781J | 19 | | | GD01851 | ST.. | 2 | | ALL |
| 5202B | 24 | G2 | | DX | 2-3 | 22-22-21 | D00675B | K15 | | | D41781J | 7 | | | ALL |
| 5202R | 24 | G2 | | DX | 0-0 | 22-22-21 | D00675B | K14 | | | D41781J | 8 | | | ALL |
| 5202Z | | | | DX | 0-0 | 22-22-21 | GD01849 | ST.. | 2 | | D41781J | 9 | | | ALL |
| FRAB | | | | | 0-0 | 22-21-21 | GD01846 | ST.. | 2 | | TB0108Y | | | AB | ALL |
| FRAC | | | | | 0-0 | 22-24-21 | GD01846 | ST.. | 2 | | TB0108Y | | | AC | ALL |
| FRAD | | | | | 0-0 | 22-24-21 | GD01841 | ST.. | 2 | | TB0108Y | | | AD | ALL |

WIRE LIST

D280N032

91-21-11

Section W1160

Page 47 End

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE | | | | | | | | | | | |
| 0001 | 24 | | GK | | 2-7 | 34-22-14 | D41073J | 28 | | | SM00001 | | WI | | ALL |
| 0002 | 24 | | GK | | 3-2 | 34-22-14 | D00081A | A09 | | | SM00001 | | WI | | ALL |
| 0003 | 24 | | GK | | 2-7 | 34-22-14 | D41073J | 29 | | | SM00002 | | WI | | ALL |
| 0004 | 24 | | GK | | 3-2 | 34-22-14 | D00081A | B09 | | | SM00002 | | WI | | ALL |
| 0005 | 24 | | GK | | 2-7 | 34-22-14 | D41073J | 30 | | | SM00003 | | WI | | ALL |
| 0006 | 24 | | GK | | 3-2 | 34-22-14 | D00081A | C09 | | | SM00003 | | WI | | ALL |
| 0007 | 24 | | GK | | 3-11 | 34-22-16 | D00081F | 1 | | | D41429J | 1 | | | 001-099 |
| 0007 | 24 | | GK | | 3-11 | 34-22-16 | D41429J | 1 | | | D00081F | 1 | | | 115-199 |
| 0008 | 22 | | GA | | 4-3 | 34-22-16 | D00081C | 1 | | | D41910J | 2 | | | 001-099 |
| 0008 | 22 | | GA | | 4-3 | 34-22-16 | D41910J | 2 | | | D00081C | 1 | | | 115-199 |
| 0009 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | F08 | | | GD01809 | ST.. | # | | 001-008, 115-199 |
| 0009 | 22 | | GA | | 3-0 | 34-22-16 | D00081B | F08 | | | GD01809 | ST.. | # | | 009-099 |
| 0010 | 22 | | GA | | 4-1 | 34-22-16 | D00081F | 4 | | | D42011J | 8 | | | 001-099 |
| 0010 | 24 | | GK | | 4-1 | 34-22-16 | D42011J | 8 | | | D00081F | 4 | | | 115-199 |
| 0011 | 20 | | GA | | 3-4 | 34-22-16 | D00081C | 4 | | | GD01810 | AC.. | 2 | | ALL |
| 0012 | 20 | | GA | | 3-4 | 34-22-16 | D00081C | 6 | | | GD01810 | ST.. | 2 | | ALL |
| 0013 | 24 | | GK | | 3-10 | 34-22-17 | D42011J | 32 | | | TB0201Z | 52 | BJ | | ALL |
| 0014 | 24 | | GK | | 3-3 | 34-22-17 | D00081A | E11 | | | TB0201Z | 52 | BJ | | 001-099 |
| 0014 | 24 | | GK | | 3-3 | 34-22-17 | TB0201Z | 52 | BJ | | D00081A | E11 | | | 115-199 |
| 0015 | 24 | | GK | | 3-10 | 34-22-17 | D42011J | 33 | | | TB0201Z | 51 | BJ | | ALL |
| 0016 | 24 | | GK | | 3-3 | 34-22-17 | D00081A | G11 | | | TB0201Z | 51 | BJ | | 001-099 |
| 0016 | 24 | | GK | | 3-3 | 34-22-17 | TB0201Z | 51 | BJ | | D00081A | G11 | | | 115-199 |
| 0017 | 24 | | GK | | 3-8 | 34-22-17 | D42011J | 34 | | | SM00007 | | WI | | ALL |
| 0018 | 24 | | GK | | 3-2 | 34-22-17 | D00081A | J12 | | | SM00007 | | WI | | 001-099 |
| 0018 | 24 | | GK | | 3-2 | 34-22-17 | SM00007 | | WI | | D00081A | J12 | | | 115-199 |
| 0019 | 24 | | GK | | 3-8 | 34-22-17 | D42011J | 35 | | | SM00008 | | WI | | ALL |
| 0020 | 24 | | GK | | 3-2 | 34-22-17 | D00081A | K12 | | | SM00008 | | WI | | 001-099 |
| 0020 | 24 | | GK | | 3-2 | 34-22-17 | SM00008 | | WI | | D00081A | K12 | | | 115-199 |
| 0021 | 24 | | GK | | 4-1 | 34-22-17 | D00081A | F12 | | | D42011J | 15 | | | 001-008, 010-099 |
| 0021 | 24 | | GK | | 3-8 | 34-22-17 | SM00065 | | WI | | D42011J | 15 | | | 009 |
| 0021 | 24 | | GK | | 3-8 | 34-22-17 | D42011J | 15 | | | SM00065 | | WI | | 115-199 |
| 0022 | 24 | | GK | | 2-7 | 34-22-15 | D41075J | 28 | | | SM00004 | | WI | | ALL |
| 0023 | 24 | | GK | | 2-7 | 34-22-15 | D41075J | 29 | | | SM00005 | | WI | | ALL |
| 0024 | 24 | | GK | | 2-7 | 34-22-15 | D41075J | 30 | | | SM00006 | | WI | | ALL |
| 0025 | 24 | | GK | | 3-2 | 34-22-15 | D00081A | F09 | | | SM00004 | | WI | | ALL |
| 0026 | 24 | | GK | | 3-2 | 34-22-15 | D00081A | G09 | | | SM00005 | | WI | | ALL |
| 0027 | 24 | | GK | | 3-2 | 34-22-15 | D00081A | H09 | | | SM00006 | | WI | | ALL |
| 0028 | 24 | | GK | | 3-2 | 34-22-15 | D00081D | F09 | | | SM00004 | | WI | | ALL |
| 0029 | 24 | | GK | | 3-2 | 34-22-15 | D00081D | G09 | | | SM00005 | | WI | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0030 | 24 | | GK | | 3-2 | 34-22-15 | D00081D | H09 | | | SM00006 | | WI | | ALL |
| 0031 | 24 | | GK | | 3-2 | 34-22-14 | D00081D | C09 | | | SM00003 | | WI | | ALL |
| 0032 | 24 | | GK | | 3-2 | 34-22-14 | D00081D | B09 | | | SM00002 | | WI | | ALL |
| 0033 | 24 | | GK | | 3-2 | 34-22-14 | D00081D | A09 | | | SM00001 | | WI | | ALL |
| 0034 | 24 | | GK | | 2-11 | 34-22-35 | D41595J | 25 | | | SM00001 | | WI | | 001-099 |
| 0034 | 24 | | GK | | 2-11 | 34-22-35 | SM00001 | | WI | | D41595J | 25 | | | 115-199 |
| 0035 | 24 | | GK | | 2-11 | 34-22-35 | D41595J | 26 | | | SM00002 | | WI | | 001-099 |
| 0035 | 24 | | GK | | 2-11 | 34-22-35 | SM00002 | | WI | | D41595J | 26 | | | 115-199 |
| 0036 | 24 | | GK | | 2-11 | 34-22-35 | D41595J | 27 | | | SM00003 | | WI | | 001-099 |
| 0036 | 24 | | GK | | 2-11 | 34-22-35 | SM00003 | | WI | | D41595J | 27 | | | 115-199 |
| 0037 | 24 | | GK | | 2-11 | 34-22-35 | D41595J | 22 | | | SM00004 | | WI | | 001-099 |
| 0037 | 24 | | GK | | 2-11 | 34-22-35 | SM00004 | | WI | | D41595J | 22 | | | 115-199 |
| 0038 | 24 | | GK | | 2-11 | 34-22-35 | D41595J | 23 | | | SM00005 | | WI | | 001-099 |
| 0038 | 24 | | GK | | 2-11 | 34-22-35 | SM00005 | | WI | | D41595J | 23 | | | 115-199 |
| 0039 | 24 | | GK | | 2-11 | 34-22-35 | D41595J | 24 | | | SM00006 | | WI | | 001-099 |
| 0039 | 24 | | GK | | 2-11 | 34-22-35 | SM00006 | | WI | | D41595J | 24 | | | 115-199 |
| 0040 | 24 | | GK | | 3-5 | 34-22-37 | D41601J | 38 | | | SM00007 | | WI | | 001-099 |
| 0040 | 24 | | GK | | 3-5 | 34-22-37 | SM00007 | | WI | | D41601J | 38 | | | 115-199 |
| 0041 | 24 | | GK | | 3-5 | 34-22-37 | D41601J | 39 | | | SM00008 | | WI | | 001-099 |
| 0041 | 24 | | GK | | 3-5 | 34-22-37 | SM00008 | | WI | | D41601J | 39 | | | 115-199 |
| 0042 | 24 | | GK | | 3-7 | 34-22-37 | D41601J | 40 | | | TB0201Z | 52 | BJ | | 001-099 |
| 0042 | 24 | | GK | | 3-7 | 34-22-37 | TB0201Z | 52 | BJ | | D41601J | 40 | | | 115-199 |
| 0043 | 24 | | GK | | 3-7 | 34-22-37 | D41601J | 41 | | | TB0201Z | 51 | BJ | | 001-099 |
| 0043 | 24 | | GK | | 3-7 | 34-22-37 | TB0201Z | 51 | BJ | | D41601J | 41 | | | 115-199 |
| 0044 | 20 | | GA | | 3-5 | 34-43-11 | D41910J | 5 | | | D41061J | 1 | | | ALL |
| 0045 | 22 | | GA | | 2-6 | 34-43-11 | D41061J | 2 | | | TB0201Z | 51 | BJ | | 001-099 |
| 0045 | 22 | | GA | | 2-6 | 34-43-11 | TB0201Z | 51 | BJ | | D41061J | 2 | | | 115-199 |
| 0046 | 24 | | GK | | 2-8 | 31-31-61 | D41093J | 26 | | | TB0201Z | 51 | BJ | | 001-099 |
| 0046 | 24 | | GK | | 2-8 | 31-31-31 | D41093J | 26 | | | TB0201Z | 51 | BJ | | 115-199 |
| 0047 | 24 | | GK | | 2-8 | 31-31-61 | D41093J | 27 | | | TB0201Z | 52 | BJ | | 001-099 |
| 0047 | 24 | | GK | | 2-8 | 31-31-31 | D41093J | 27 | | | TB0201Z | 52 | BJ | | 115-199 |
| 0048 | 24 | | GK | | 2-6 | 31-51-21 | D41091J | 1 | | | SM00011 | | WI | | 001-008, 115-199 |
| 0048 | 24 | | GK | | 2-0 | 31-51-21 | D41091J | 1 | | | SM00011 | | WI | | 009-099 |
| 0049 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | E10 | | | GD01809 | ST.. | 2 | | 001-008, 115-199 |
| 0049 | 22 | | GA | | 3-0 | 34-22-16 | D00081B | E10 | | | GD01809 | ST.. | 2 | | 009-099 |
| 0050 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | F09 | | | GD01809 | ST.. | 2 | | 001-008 |
| 0050 | 22 | | GA | | 3-0 | 34-22-16 | D00081B | F09 | | | GD01809 | ST.. | 2 | | 009-099 |
| 0050 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | F09 | | | GD01809 | ST.. | # | | 115-199 |
| 0051 | 20 | | GA | | 1-6 | 34-22-19 | D41563J | | | DH | GD01812 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 2

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|-------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0051 | 20 | | GA | | 1-6 | 34-22-19 | GD01812 | ST.. | 2 | | D41563J | | | DH | 115-199 |
| 0052 | 20 | | GA | | 1-6 | 34-22-18 | D41601J | | | CW | GD01812 | ST.. | 2 | | 001-099 |
| 0052 | 20 | | GA | | 1-6 | 34-22-18 | GD01812 | ST.. | 2 | | D43023J | | | RT | 115-199 |
| 0053 | 20 | | GA | | 1-6 | 34-22-18 | D41391J | | | CX | GD01802 | ST.. | 2 | | 001-099 |
| 0053 | 20 | | GA | | 2-6 | 34-22-18 | GD01802 | ST.. | 2 | | D41391J | | | CX | 115-199 |
| 0054 | 24 | | GK | | 4-10 | 34-12-12 | D00289B | F02 | | | D41091J | 49 | | | 001-099 |
| 0054 | 24 | | GK | | 4-10 | 34-12-12 | D41091J | | 49 | | D00289B | F02 | | | 115-199 |
| 0055 | 22 | | GA | | 0-7 | 34-12-12 | D00289B | F15 | | | SM00009 | | WI | | ALL |
| 0056 | 22 | | GA | | 0-7 | 34-12-12 | D00289B | F05 | | | SM00009 | | WI | | ALL |
| 0057 | 22 | | GA | | 0-7 | 34-12-12 | D00289B | H15 | | | SM00009 | | WI | | ALL |
| 0058 | 24 | | GK | | 4-10 | 34-12-12 | D00289B | E10 | | | D41091J | 50 | | | 001-099 |
| 0058 | 24 | | GK | | 4-10 | 34-12-12 | D41091J | | 50 | | D00289B | E10 | | | 115-199 |
| 0059 | 24 | | GK | | 1-9 | 34-12-12 | TB0201Z | 119 | BJ | | TB0201Z | 121 | BJ | | ALL |
| 0060 | 24 | | GK | | 1-9 | 34-12-12 | TB0201Z | 120 | BJ | | TB0201Z | 122 | BJ | | ALL |
| 0061 | 24 | | GK | | 4-8 | 34-12-12 | D00289B | E09 | | | D41093J | 25 | | | ALL |
| 0062 | 22 | | GA | | 0-7 | 34-12-12 | D00289B | D02 | | | SM00009 | | WI | | 001-099 |
| 0062 | 24 | | GK | | 0-7 | 34-12-12 | D00289B | D02 | | | SM00009 | | WI | | 115-199 |
| 0063 | 22 | | GA | | 0-7 | 34-12-12 | D00289B | G03 | | | SM00009 | | WI | | 001-099 |
| 0063 | 24 | | GK | | 0-7 | 34-12-12 | D00289B | G03 | | | SM00009 | | WI | | 115-199 |
| 0064 | 22 | | GA | | 3-11 | 34-12-12 | D00289B | D06 | | | GD01812 | DC.. | 2 | | 001-010 |
| 0064 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | D06 | | | TB0201Z | 90 | BJ | | 011-099 |
| 0065 | 24 | | GK | | 4-10 | 34-12-12 | D00289B | E03 | | | SM00013 | | WI | | ALL |
| 0066 | 24 | | GK | | 3-8 | 34-12-12 | D42011J | 24 | | | SM00011 | | WI | | ALL |
| 0067 | 22 | | GA | | 0-7 | 34-12-12 | D00289B | D14 | | | D00289B | E14 | | | 001-099 |
| 0067 | 24 | | GK | | 0-7 | 34-12-12 | D00289B | D14 | | | D00289B | E14 | | | 115-199 |
| 006CO | | | | MF | 0-0 | 34-45-02 | D41199J | = C1 | | | D01583C | = C12 | | | ALL |
| 006CX | | 66 | | MF | 1-8 | 34-45-02 | D41199J | = A1 | | | D01583C | 12 | | | 001-099 |
| 006CX | | 66 | | MF | 1-2 | 34-45-02 | D41199J | = A1 | | | D01583C | 12 | | | 115-199 |
| 0070 | 22 | | GA | | 4-2 | 34-12-12 | D00289B | F10 | | | GD01811 | DC.. | 2 | | 001-099 |
| 0070 | 22 | | GA | | 4-2 | 34-12-12 | GD01811 | DC.. | 2 | | D00289B | F10 | | | 115-199 |
| 0071 | 22 | | GA | | 3-0 | 34-22-16 | D42013J | 27 | | | SM00026 | | WI | | 001-099 |
| 0071 | 22 | | GA | | 3-0 | 34-22-16 | D42013J | 36 | | | SM00026 | | WI | | 115-199 |
| 0073 | 22 | | GA | | 3-8 | 34-12-11 | D41093J | 23 | | | D41910J | 8 | | | 001-099 |
| 0073 | 22 | | GA | | 3-8 | 34-12-11 | D41910J | 8 | | | D41093J | 23 | | | 115-199 |
| 0074 | 22 | | GA | | 4-9 | 34-12-11 | D41910J | 9 | | | TB0201Z | 114 | BJ | | ALL |
| 0075 | 16 | | GA | | 4-2 | 34-12-11 | D00289C | 7 | | | GD01811 | AC.. | 2 | | 001-099 |
| 0075 | 16 | | GA | | 4-2 | 34-12-11 | GD01811 | AC.. | 2 | | D00289C | 7 | | | 115-199 |
| 0076 | 16 | | GA | | 4-2 | 34-12-11 | D00289C | 8 | | | GD01811 | ST.. | 2 | | 001-099 |
| 0076 | 16 | | GA | | 4-2 | 34-12-11 | GD01811 | ST.. | 2 | | D00289C | 8 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0077 | 22 | | GA | | 2-5 | 34-12-11 | D41910J | 13 | | | SM00012 | | WI | | ALL |
| 0078 | 22 | | GA | | 2-7 | 34-12-11 | D41093J | 24 | | | GD01811 | AC.. | 2 | | 001-099 |
| 0078 | 22 | | GA | | 2-7 | 34-12-11 | GD01811 | AC.. | 2 | | D41093J | 24 | | | 115-199 |
| 007CO | | | | MG | 0-0 | 34-45-02 | D01583A | = C1 | | | D41181J | = C1 | | | ALL |
| 007CX | | | CW | MG | 1-7 | 34-45-02 | D01583A | 1 | | | D41181J | = A1 | | | 001-099 |
| 007CX | | | CW | MG | 1-2 | 34-45-02 | D01583A | 1 | | | D41181J | = A1 | | | 115-199 |
| 0080 | 24 | | GK | | 0-7 | 34-12-12 | TB0201Z | 120 | BJ | | TB0201Z | 118 | BJ | | ALL |
| 0081 | 24 | | GK | | 0-7 | 34-12-12 | TB0201Z | 119 | BJ | | TB0201Z | 117 | BJ | | ALL |
| 0083 | 22 | | GA | | 2-9 | 34-51-11 | D43003J | 11 | | | SM00020 | | WI | | 001-099 |
| 0083 | 22 | | GA | | 3-9 | 34-51-11 | SM00020 | | WI | | D41831J | 1 | | | 115-199 |
| 0084 | 22 | | GA | | 2-9 | 34-31-11 | D43003J | 24 | | | SM00020 | | WI | | ALL |
| 008CO | | | | MH | 0-0 | 34-45-02 | D01583A | = C2 | | | D41185J | = C1 | | | ALL |
| 008CX | | | CW | MH | 1-7 | 34-45-02 | D01583A | 2 | | | D41185J | = A1 | | | ALL |
| 0091 | 22 | | GA | | 4-2 | 34-31-11 | D00081A | E12 | | | D43003J | 23 | | | 001-099 |
| 0091 | 22 | | GA | | 4-2 | 34-31-11 | D43003J | 23 | | | D00081A | E12 | | | 115-199 |
| 0092 | 24 | | GK | | 3-0 | 34-33-11 | D41089J | 50 | | | SM00020 | | WI | | ALL |
| 0093 | 22 | | GA | | 3-0 | 34-51-11 | D42013J | 14 | | | SM00021 | | WI | | ALL |
| 0094 | 24 | | GK | | 4-10 | 34-12-22 | D00289B | F11 | | | D41745J | 10 | | | ALL |
| 0096 | 22 | | GA | | 4-0 | 34-61-14 | D00173A | K04 | | | SM00026 | | WI | | ALL |
| 0097 | 22 | | GA | | 2-9 | 34-51-11 | D43003J | 4 | | | SM00021 | | WI | | 001-099 |
| 0097 | 22 | | GA | | 3-9 | 34-51-11 | SM00021 | | WI | | D41831J | 5 | | | 115-199 |
| 0098 | 24 | | GK | | 3-0 | 34-55-11 | D41089J | 48 | | | SM00020 | | WI | | 001-099 |
| 0098 | 24 | | GK | | 3-0 | 34-55-11 | SM00020 | | WI | | D41089J | 48 | | | 115-199 |
| 0099 | 24 | | GK | | 3-0 | 34-55-11 | D41089J | 49 | | | SM00020 | | WI | | 001-099 |
| 0099 | 24 | | GK | | 3-0 | 34-55-11 | SM00020 | | WI | | D41089J | 49 | | | 115-199 |
| 009CO | | | | MI | 0-0 | 34-45-02 | D01583A | = C3 | | | D41187J | = C1 | | | ALL |
| 009CX | | | CW | MI | 1-7 | 34-45-02 | D01583A | 3 | | | D41187J | = A1 | | | ALL |
| 0101 | 22 | | GA | | 2-6 | 22-14-11 | D41595J | 39 | | | SM00061 | | WI | | ALL |
| 0102 | 22 | | GA | | 2-6 | 22-14-11 | D41595J | 40 | | | SM00062 | | WI | | ALL |
| 0103 | 22 | | GA | | 2-6 | 22-14-11 | D41595J | 41 | | | SM00064 | | WI | | ALL |
| 0104 | 22 | | GA | | 2-11 | 22-14-11 | D00035B | K03 | | | D41595J | 42 | | | 001-099 |
| 0104 | 22 | | GA | | 2-11 | 22-14-11 | D41595J | 42 | | | D00035B | K03 | | | 115-199 |
| 0105 | 22 | | GA | | 2-6 | 22-14-11 | D41595J | 50 | | | SM00063 | | WI | | ALL |
| 0106 | 22 | | GA | | 4-1 | 22-14-11 | D42011J | 31 | | | SM00016 | | WI | | ALL |
| 0107 | 22 | | GA | | 2-6 | 22-14-11 | D41091J | 27 | | | SM00017 | | WI | | ALL |
| 0108 | 22 | | GA | | 3-6 | 22-14-11 | D00035B | E12 | | | SM00017 | | WI | | ALL |
| 0109 | 16 | | GA | | 1-9 | 75-31-11 | TB0201B | A105 | 2 | | GD01812 | DC.. | 2 | | ALL |
| 010CO | | | | MK | 0-0 | 34-45-02 | D01583A | = C4 | | | D41189J | = C1 | | | ALL |
| 010CX | | | CW | MK | 1-7 | 34-45-02 | D01583A | 4 | | | D41189J | = A1 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 4

Jan 21/2005



WIRE LIST
D280N032

91-21-11
Section W1170
Page 5
Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1171 | 286N1171 | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 015CO | | MO | 0-0 | 34-45-02 | D01583B | = C4 | | | D41197J | = C1 | | | ALL | | |
| 015CX | | CW | 1-7 | 34-45-02 | D01583B | 4 | | | D41197J | = A1 | | | ALL | | |
| 0160 | 24 | GK | 4-5 | 34-61-14 | D00173A | K01 | | | SM00047 | | WI | | ALL | | |
| 0161 | 24 | GK | 4-5 | 34-61-14 | D00173A | F09 | | | SM00047 | | WI | | ALL | | |
| 0162 | 24 | GK | 3-2 | 34-61-14 | D00173B | G15 | | | D42183J | 11 | | | 001-099 | | |
| 0162 | 24 | GK | 3-2 | 34-61-14 | D42183J | 11 | | | D00173B | G15 | | | 115-199 | | |
| 0163 | 20 | GA | 1-6 | 34-61-14 | D42183J | | | BA | GD01812 | ST.. | 2 | | ALL | | |
| 0164 | 22 | GA | 2-9 | 34-61-15 | D41339J | 1 | | | D42183J | 13 | | | 001-008, 115-199 | | |
| 0164 | 22 | GA | 4-5 | 34-61-15 | D41910J | 16 | | | D42183J | 13 | | | 009-099 | | |
| 0165 | 22 | GA | 4-1 | 34-61-15 | D42011J | 9 | | | SM00049 | | WI | | ALL | | |
| 0166 | 22 | GA | 4-5 | 34-61-15 | D00173A | K13 | | | SM00049 | | WI | | ALL | | |
| 0168 | 20 | GA | 3-6 | 34-61-15 | D42183J | 14 | | | GD01806 | AC.. | 2 | | ALL | | |
| 0169 | 20 | GA | 3-6 | 34-61-15 | D42183J | 15 | | | GD01806 | AC.. | 2 | | ALL | | |
| 0170 | 24 | GK | 3-9 | 34-61-15 | D00173B | K07 | | | D41089J | 21 | | | 001-099 | | |
| 0170 | 24 | GK | 3-9 | 34-61-15 | D41089J | 21 | | | D00173B | K07 | | | 115-199 | | |
| 0171 | 22 | GA | 3-4 | 34-61-15 | D41089J | 22 | | | SM00049 | | WI | | ALL | | |
| 0172 | 20 | GA | 1-6 | 34-61-15 | D42183J | | | BD | GD01812 | ST.. | 2 | | 001-010, 115-199 | | |
| 0172 | 20 | GA | 1-6 | 34-61-15 | D42183J | | | BD | GD01812 | ST.. | 2 | *3 | 011-099 | | |
| 0173 | 20 | GA | 1-6 | 34-61-21 | D41601J | | | BI | GD01812 | ST.. | 2 | | 001-010 | | |
| 0173 | 20 | GA | 1-6 | 34-61-21 | D41601J | | | BI | GD01812 | ST.. | 2 | *3 | 011-099 | | |
| 0173 | 20 | GA | 1-6 | 34-61-21 | GD01812 | ST.. | 2 | | D41601J | | | BI | 115-199 | | |
| 0174 | 24 | GK | 3-4 | 34-61-21 | D00173A | J13 | | | D41601J | 21 | | | 001-099 | | |
| 0174 | 24 | PK | 3-4 | 34-61-21 | D00173A | CAP | Y | | D41601J | 21 | | | 115-199 | | |
| 0175 | 20 | GA | 1-6 | 34-61-21 | D41601J | | | BJ | GD01812 | ST.. | 2 | | 001-010 | | |
| 0175 | 20 | GA | 1-6 | 34-61-21 | D41601J | | | BJ | GD01812 | ST.. | 2 | *2 | 011-099 | | |
| 0175 | 20 | GA | 1-6 | 34-61-21 | GD01812 | ST.. | 2 | | D41601J | | | BJ | 115-199 | | |
| 0176 | 20 | GA | 1-6 | 34-61-21 | D41601J | | | BK | GD01812 | ST.. | 2 | | 001-010 | | |
| 0176 | 20 | GA | 1-6 | 34-61-21 | D41601J | | | BK | GD01812 | ST.. | 2 | *2 | 011-099 | | |
| 0176 | 20 | GA | 1-6 | 34-61-21 | GD01812 | ST.. | 2 | | D41601J | | | BK | 115-199 | | |
| 0177 | 20 | GA | 1-6 | 34-61-11 | D41081J | | | AI | GD01812 | ST.. | 2 | | 001-008, 010, 115-199 | | |
| 0177 | 20 | GA | 1-6 | 34-61-11 | D41081J | | | AI | GD01812 | ST.. | 2 | *1 | 009, 011-099 | | |
| 0178 | 20 | GA | 1-6 | 34-61-12 | D41563J | | | AK | GD01812 | ST.. | 2 | *1 | 001-099 | | |
| 0178 | 20 | GA | 1-6 | 34-61-12 | D41563J | | | AK | GD01812 | ST.. | 2 | | 115-199 | | |
| 0179 | 24 | GK | 3-2 | 34-61-23 | D41563J | 21 | | | SM00021 | | WI | | 001-099 | | |
| 0179 | 24 | GK | 3-2 | 34-61-23 | SM00021 | | WI | | D41563J | 21 | | | 115-199 | | |
| 0180 | 24 | GK | 3-0 | 34-12-12 | D41089J | 52 | | | SM00011 | | WI | | ALL | | |
| 0181 | 24 | GK | 3-2 | 34-61-23 | D41563J | 22 | | | SM00029 | | WI | | 001-099 | | |
| 0181 | 24 | GK | 3-2 | 34-61-23 | SM00029 | | WI | | D41563J | 22 | | | 115-199 | | |
| 0182 | 24 | GK | 3-2 | 34-61-23 | D41563J | 26 | | | SM00030 | | WI | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 0182 | 24 | | GK | | 3-2 | 34-61-23 | SM00030 | | WI | | D41563J | 26 | | | 115-199 |
| 0183 | 24 | | GK | | 3-2 | 34-61-23 | D41563J | 27 | | | SM00031 | | WI | | 001-099 |
| 0183 | 24 | | GK | | 3-2 | 34-61-23 | SM00031 | | WI | | D41563J | 27 | | | 115-199 |
| 0184 | 24 | | GK | | 3-6 | 34-61-23 | D41563J | 28 | | | SM00032 | | WI | | 001-099 |
| 0184 | 24 | | GK | | 3-6 | 34-61-23 | SM00032 | | WI | | D41563J | 28 | | | 115-199 |
| 0185 | 24 | | GK | | 3-6 | 34-61-23 | D41563J | 29 | | | SM00033 | | WI | | 001-099 |
| 0185 | 24 | | GK | | 3-6 | 34-61-23 | SM00033 | | WI | | D41563J | 29 | | | 115-199 |
| 0186 | 24 | | GK | | 3-6 | 34-61-23 | D41563J | 30 | | | SM00034 | | WI | | 001-099 |
| 0186 | 24 | | GK | | 3-6 | 34-61-23 | SM00034 | | WI | | D41563J | 30 | | | 115-199 |
| 0187 | 24 | | GK | | 3-2 | 34-61-23 | D41563J | 31 | | | SM00035 | | WI | | 001-099 |
| 0187 | 24 | | GK | | 3-2 | 34-61-23 | SM00035 | | WI | | D41563J | 31 | | | 115-199 |
| 0188 | 24 | | GK | | 3-6 | 34-61-23 | D41563J | 32 | | | SM00036 | | WI | | 001-099 |
| 0188 | 24 | | GK | | 3-6 | 34-61-23 | SM00036 | | WI | | D41563J | 32 | | | 115-199 |
| 0189 | 24 | | GK | | 3-6 | 34-61-23 | D41563J | 33 | | | SM00037 | | WI | | 001-099 |
| 0189 | 24 | | GK | | 3-6 | 34-61-23 | SM00037 | | WI | | D41563J | 33 | | | 115-199 |
| 0191 | 24 | | GK | | 3-9 | 34-61-25 | D41601J | 34 | | | SM00049 | | WI | | 001-099 |
| 0191 | 24 | | GK | | 3-9 | 34-61-25 | SM00049 | | WI | | D41601J | 34 | | | 115-199 |
| 0194 | 22 | | GA | | 4-3 | 22-41-11 | D00035A | A03 | | | D41091J | 43 | | | ALL |
| 0195 | 22 | | GA | | 3-6 | 22-32-15 | D41563J | 50 | | | SM00046 | | WI | | 001-099 |
| 0195 | 22 | | GA | | 3-6 | 22-32-15 | SM00046 | | WI | | D41563J | 50 | | | 115-199 |
| 0197 | 22 | | GA | | 2-6 | 22-22-11 | D41091J | 35 | | | SM00039 | | WI | | ALL |
| 0198 | 22 | | GA | | 3-10 | 34-12-12 | D00289B | E07 | | | GD01814 | DC.. | 2 | | 009 |
| 0198 | 24 | | GK | | 4-1 | 34-12-12 | D00289B | E07 | | | TB0201X | A085 | BJ | | 011-099 |
| 0198 | 24 | | GK | | 3-10 | 34-12-12 | D00289B | E07 | | | GD01814 | DC.. | # | | 115-199 |
| 0199 | 20 | | GA | | 3-2 | 22-11-11 | D00035C | 6 | | | D41910J | 7 | | | 001-099 |
| 0199 | 20 | | GA | | 3-2 | 22-11-11 | D41910J | 7 | | | D00035C | 6 | | | 115-199 |
| 0200 | 20 | | GA | | 2-11 | 22-11-11 | D00035C | 7 | | | GD01803 | ST.. | 2 | | ALL |
| 0201 | 20 | | GA | | 2-11 | 22-11-11 | D00035C | 4 | | | GD01803 | AC.. | 2 | | ALL |
| 0202 | 20 | | GA | | 2-5 | 22-11-12 | D41910J | 10 | | | SM00016 | | WI | | ALL |
| 0203 | 20 | | GA | | 3-6 | 22-11-12 | D00035C | 2 | | | SM00042 | | WI | | 001-099 |
| 0203 | 20 | | GA | | 3-6 | 22-11-12 | SM00042 | | WI | | D00035C | 2 | | | 115-199 |
| 0204 | 20 | | GA | | 3-6 | 22-11-12 | D00035C | 5 | | | SM00042 | | WI | | 001-099 |
| 0204 | 20 | | GA | | 3-6 | 22-11-12 | SM00042 | | WI | | D00035C | 5 | | | 115-199 |
| 0205 | 22 | | GA | | 3-6 | 22-11-12 | D00035C | 1 | | | SM00042 | | WI | | 001-099 |
| 0205 | 22 | | GA | | 3-6 | 22-11-12 | SM00042 | | WI | | D00035C | 1 | | | 115-199 |
| 0206 | 20 | | GA | | 2-10 | 22-11-12 | D41910J | 11 | | | SM00042 | | WI | | ALL |
| 0207 | 22 | | GA | | 3-0 | 22-11-12 | D42013J | 1 | | | SM00042 | | WI | | ALL |
| 0208 | 22 | | GA | | 2-7 | 22-11-12 | D42013J | 3 | | | SM00043 | | WI | | ALL |
| 0209 | 22 | | GA | | 3-1 | 22-11-12 | D00035A | H15 | | | SM00043 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 8

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0209 | 22 | | GA | | 3-1 | 22-11-12 | SM00043 | | WI | | D00035A | H15 | | | 115-199 | |
| 0210 | 22 | | GA | | 3-1 | 22-11-12 | D00035B | H15 | | | SM00043 | | WI | | 001-099 | |
| 0210 | 22 | | GA | | 3-1 | 22-11-12 | SM00043 | | WI | | D00035B | H15 | | | 115-199 | |
| 0211 | 22 | | GA | | 3-0 | 22-11-12 | D42013J | 2 | | | D00035B | G11 | | | 115-199 | |
| 0213 | 22 | | GA | | 2-7 | 22-11-12 | D42013J | 4 | | | SM00016 | | WI | | ALL | |
| 0214 | 22 | | GA | | 2-11 | 22-11-12 | D00035B | F15 | | | D41701J | 1 | | | 001-099 | |
| 0214 | 22 | | GA | | 2-11 | 22-11-12 | D41701J | 1 | | | D00035B | F15 | | | 115-199 | |
| 0215 | 22 | | GA | | 0-7 | 22-11-12 | D00035B | G13 | | | D00035B | H14 | | | 115-199 | |
| 0217 | 22 | | GA | | 3-6 | 22-11-12 | D00035B | H11 | | | SM00045 | | WI | | ALL | |
| 0218 | 22 | | GA | | 2-11 | 22-11-12 | D41701J | 2 | | | SM00045 | | WI | | ALL | |
| 0219 | 20 | | GA | | 2-4 | 22-11-12 | D41701J | 3 | | | GD01803 | DC.. | 2 | | ALL | |
| 0220 | 20 | | GA | | 2-4 | 22-11-12 | D41701J | 4 | | | GD01803 | DC.. | 2 | | ALL | |
| 0221 | 22 | | GA | | 2-11 | 22-11-12 | D41701J | 5 | | | SM00045 | | WI | | ALL | |
| 0222 | 20 | | GA | | 2-4 | 22-11-12 | D41701J | 6 | | | GD01803 | DC.. | 2 | | ALL | |
| 0223 | 22 | | GA | | 0-7 | 22-11-12 | D00035A | A13 | | | D00035A | A14 | | | 001-008, 115-199 | |
| 0223 | 22 | | GA | | 0-7 | 22-11-13 | D00035A | A13 | | | D00035A | A14 | | | 009-099 | |
| 0224 | 22 | | GA | | 0-7 | 22-11-12 | D00035A | A12 | | | D00035A | A11 | | | 001-008, 115-199 | |
| 0224 | 22 | | GA | | 0-7 | 22-11-13 | D00035A | A12 | | | D00035A | A11 | | | 009-099 | |
| 0226 | 22 | | GA | | 4-1 | 22-11-12 | D00035B | A06 | | | D41905J | 22 | | | ALL | |
| 0227 | 22 | | GA | | 4-1 | 22-11-12 | D00035B | C07 | | | D41905J | 23 | | | ALL | |
| 0228 | 22 | | GA | | 2-8 | 22-11-12 | D00035A | C15 | | | D41606J | 20 | | | ALL | |
| 0229 | 22 | | GA | | 2-8 | 22-11-12 | D00035B | C15 | | | D41606J | 2 | | | ALL | |
| 0230 | 22 | | GA | | 0-7 | 22-11-12 | D00035B | A03 | | | D00035B | E04 | | | 001-008, 115-199 | |
| 0231 | 22 | | GA | | 2-9 | 22-11-12 | D00035B | A15 | | | D41691J | 1 | | | ALL | |
| 0232 | 22 | | GA | | 2-9 | 22-11-12 | D00035A | A15 | | | D41691J | 29 | | | ALL | |
| 0233 | 22 | | GA | | 2-11 | 22-11-12 | D00035A | A04 | | | GD01803 | DC.. | 2 | | ALL | |
| 0234 | 22 | | GA | | 2-11 | 22-11-12 | D00035A | G11 | | | GD01803 | DC.. | 2 | | ALL | |
| 0236 | 22 | | GA | | 2-9 | 22-11-12 | D00035B | K15 | | | D41691J | 17 | | | ALL | |
| 0237 | 22 | | GA | | 2-9 | 22-11-12 | D00035A | K15 | | | D41691J | 31 | | | ALL | |
| 0240 | 22 | | GA | | 3-6 | 22-12-11 | D00035B | G09 | | | SM00039 | | WI | | 001-099 | |
| 0240 | 22 | | GA | | 3-6 | 22-12-11 | SM00039 | | WI | | D00035B | G09 | | | 115-199 | |
| 0241 | 22 | | GA | | 3-6 | 22-12-11 | D00035A | G09 | | | SM00039 | | WI | | 001-099 | |
| 0241 | 22 | | GA | | 3-6 | 22-12-11 | SM00039 | | WI | | D00035A | G09 | | | 115-199 | |
| 0242 | 20 | | GA | | 2-5 | 22-12-11 | D41701J | 7 | | | GD01802 | DC.. | 2 | | ALL | |
| 0243 | 22 | | GA | | 2-6 | 22-12-11 | D41701J | 8 | | | SM00046 | | WI | | ALL | |
| 0244 | 22 | | GA | | 3-1 | 22-12-11 | D00035A | F15 | | | SM00046 | | WI | | ALL | |
| 0245 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | D10 | | | GD01809 | ST.. | # | | 001-008, 115-199 | |
| 0245 | 22 | | GA | | 3-0 | 34-22-16 | D00081B | D10 | | | GD01809 | ST.. | # | | 009-099 | |
| 0246 | 22 | | GA | | 4-3 | 22-12-11 | D00035B | D08 | | | D41091J | 23 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 9

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0247 | 22 | | GA | | 4-3 | 22-12-11 | D00035B | C09 | | | D41091J | 24 | | | ALL |
| 0248 | 22 | | GA | | 4-3 | 22-12-11 | D00035B | D10 | | | D41091J | 25 | | | ALL |
| 0249 | 22 | | GA | | 4-3 | 22-12-11 | D00035B | D09 | | | D41091J | 26 | | | ALL |
| 0250 | 22 | | GA | | 4-3 | 22-12-11 | D00035A | F12 | | | D41091J | 36 | | | ALL |
| 0251 | 22 | | GA | | 4-3 | 22-12-11 | D00035B | E10 | | | D41091J | 22 | | | ALL |
| 0252 | 22 | | GA | | 4-1 | 22-13-11 | D00035B | H03 | | | D41905J | 10 | | | 001-099 |
| 0252 | 22 | | GA | | 3-6 | 22-13-11 | D00035B | H03 | | | D43003J | 42 | | | 115-199 |
| 0259 | 22 | | GA | | 2-4 | 22-14-31 | D41905J | 20 | | | SM00019 | | WI | | ALL |
| 0260 | 22 | | GA | | 2-4 | 22-14-31 | D41905J | 24 | | | SM00019 | | WI | | ALL |
| 0263 | 22 | | GA | | 2-4 | 22-14-31 | D41905J | 21 | | | SM00017 | | WI | | ALL |
| 0265 | 22 | | GA | | 2-6 | 22-15-12 | D41595J | 48 | | | SM00052 | | WI | | ALL |
| 0266 | 22 | | GA | | 2-6 | 22-15-12 | D41595J | 49 | | | SM00052 | | WI | | ALL |
| 0267 | 22 | | GA | | 3-1 | 22-15-12 | D00035A | G10 | | | SM00052 | | WI | | 001-099 |
| 0267 | 22 | | GA | | 3-1 | 22-15-12 | SM00052 | | WI | | D00035A | G10 | | | 115-199 |
| 0269 | 24 | | GK | | 2-6 | 34-43-12 | D41061J | 6 | | | D41073J | 34 | | | 001, 003-099, 115-199 |
| 0269 | 22 | | GA | | 5-0 | 34-43-12 | D41061J | 6 | | | TB0201Y | C064 | BJ | | 002 |
| 0270 | 20 | | GA | | 1-6 | 22-12-21 | D41745J | | | CH | GD01809 | ST.. | 2 | | ALL |
| 0271 | 24 | | GK | | 2-11 | 34-61-13 | D41093J | 4 | | | SM00053 | | WI | | ALL |
| 0272 | 24 | | GK | | 4-5 | 34-61-13 | D00173B | E14 | | | SM00053 | | WI | | ALL |
| 0273 | 24 | | GK | | 2-11 | 34-61-13 | D41093J | 5 | | | SM00054 | | WI | | ALL |
| 0274 | 24 | | GK | | 4-5 | 34-61-13 | D00173B | H13 | | | SM00054 | | WI | | ALL |
| 0275 | 24 | | GK | | 2-11 | 34-61-13 | D41093J | 6 | | | SM00055 | | WI | | ALL |
| 0276 | 24 | | GK | | 4-5 | 34-61-13 | D00173B | H14 | | | SM00055 | | WI | | ALL |
| 0277 | 24 | | GK | | 2-6 | 34-61-13 | D41093J | 7 | | | SM00056 | | WI | | ALL |
| 0278 | 24 | | GK | | 4-0 | 34-61-13 | D00173B | D14 | | | SM00056 | | WI | | ALL |
| 0279 | 24 | | GK | | 3-11 | 34-61-23 | D41817J | 9 | | | SM00053 | | WI | | ALL |
| 0280 | 24 | | GK | | 3-7 | 34-61-23 | D41817J | 10 | | | SM00056 | | WI | | ALL |
| 0281 | 24 | | GK | | 3-11 | 34-61-23 | D41817J | 11 | | | SM00054 | | WI | | ALL |
| 0282 | 24 | | GK | | 3-11 | 34-61-23 | D41817J | 12 | | | SM00055 | | WI | | ALL |
| 0283 | 22 | | GA | | 0-7 | 22-11-12 | D00035B | K13 | | | D00035B | K14 | | | 001-008 |
| 0284 | 20 | | GA | | 2-2 | 31-31-42 | D41093J | | | FH | GD01809 | ST.. | 2 | | 001-099 |
| 0284 | 20 | | GA | | 1-6 | 31-31-22 | GD01809 | ST.. | 2 | | D41093J | | | FF | 115-199 |
| 0285 | 22 | | GA | | 2-4 | 22-14-21 | D41905J | 18 | | | SM00017 | | WI | | ALL |
| 0289 | 22 | | GA | | 2-4 | 22-14-21 | D41905J | 19 | | | SM00019 | | WI | | ALL |
| 0290 | 20 | | GA | | 1-6 | 22-15-11 | D41091J | | | GE | GD01806 | ST.. | 2 | | ALL |
| 0291 | 20 | | GA | | 1-6 | 22-15-11 | D41391J | | | GF | GD01802 | ST.. | 2 | | ALL |
| 0292 | 20 | | GA | | 1-6 | 22-15-11 | D41595J | | | GG | GD01802 | ST.. | 2 | | ALL |
| 0293 | 20 | | GA | | 1-6 | 22-15-11 | D41745J | | | GH | GD01809 | ST.. | 2 | | ALL |
| 0294 | 20 | | GA | | 1-6 | 22-41-11 | D41091J | | | EX | GD01806 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 10

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0294 | 20 | | GA | | 1-6 | 22-41-11 | GD01806 | ST.. | 2 | | D41091J | | | EX | 115-199 |
| 0296 | 20 | | GA | | 1-6 | 22-41-12 | D41093J | | | EW | GD01809 | ST.. | 2 | | 001-099 |
| 0296 | 20 | | GA | | 1-6 | 22-41-12 | GD01809 | ST.. | 2 | | D41093J | | | EW | 115-199 |
| 0297 | 20 | | GA | | 1-6 | 22-12-31 | D41391J | | | FR | GD01802 | ST.. | 2 | | ALL |
| 0298 | 20 | | GA | | 1-6 | 22-13-11 | D41595J | | | FX | GD01802 | ST.. | 2 | | ALL |
| 0299 | 20 | | GA | | 1-6 | 22-12-11 | D41091J | | | CC | GD01806 | ST.. | 2 | | ALL |
| 0301 | 22 | | GA | | 3-11 | 34-12-12 | D00289B | J06 | | | GD01812 | DC.. | 2 | | 001-099 |
| 0301 | 22 | | GA | | 3-11 | 34-12-12 | GD01812 | DC.. | 2 | | D00289B | J06 | | | 115-199 |
| 0302 | 22 | | GA | | 3-6 | 34-12-11 | D00289C | | 9 | | GD01815 | AC.. | 2 | | ALL |
| 0303 | 22 | | GA | | 3-3 | 34-12-11 | D00289C | | 5 | | TB0201Z | 114 | BJ | | ALL |
| 0304 | 22 | | GA | | 2-3 | 34-12-11 | D42129J | | 8 | | TB0201Z | 114 | BJ | | 001-099 |
| 0304 | 22 | | GA | | 2-3 | 34-12-11 | TB0201Z | | 114 | BJ | D42129J | 8 | | | 115-199 |
| 0305 | 22 | | GA | | 2-6 | 34-12-11 | D42129J | | 9 | | GD01815 | AC.. | 2 | | 001-099 |
| 0305 | 22 | | GA | | 2-6 | 34-12-11 | GD01815 | AC.. | 2 | | D42129J | 9 | | | 115-199 |
| 0306 | 22 | | GA | | 2-6 | 34-12-11 | D42129J | | 2 | | GD01815 | AC.. | 2 | | 001-099 |
| 0306 | 22 | | GA | | 2-6 | 34-12-11 | GD01815 | AC.. | 2 | | D42129J | 2 | | | 115-199 |
| 0307 | 22 | | GA | | 2-3 | 34-12-11 | D42129J | | 1 | | TB0201Z | 114 | BJ | | 001-099 |
| 0307 | 22 | | GA | | 2-3 | 34-12-11 | TB0201Z | | 114 | BJ | D42129J | 1 | | | 115-199 |
| 0308 | 22 | | GA | | 2-9 | 34-12-11 | D42065J | | 8 | | GD01815 | AC.. | 2 | | ALL |
| 0309 | 22 | | GA | | 4-2 | 34-12-11 | D42065J | | 7 | | SM00012 | | WI | | ALL |
| 0310 | 22 | | GA | | 2-4 | 34-12-11 | D42011J | | 23 | | GD01815 | AC.. | 2 | | ALL |
| 0311 | 22 | | GA | | 4-1 | 34-12-11 | D42011J | | 22 | | SM00012 | | WI | | ALL |
| 0312 | 22 | | GA | | 2-4 | 34-12-11 | D42011J | | 14 | | GD01815 | AC.. | 2 | | 115-199 |
| 0313 | 22 | | GA | | 4-1 | 34-12-11 | D42011J | | 13 | | SM00012 | | WI | | 115-199 |
| 0314 | 22 | | GA | | 3-6 | 34-12-11 | D00289C | | 11 | | GD01815 | AC.. | 2 | | ALL |
| 0315 | 22 | | GA | | 3-3 | 34-12-11 | D00289C | | 10 | | TB0201Z | 114 | BJ | | 001-099 |
| 0315 | 22 | | GA | | 3-3 | 34-12-11 | TB0201Z | | 114 | BJ | D00289C | 10 | | | 115-199 |
| 0316 | 22 | | GA | | 3-6 | 34-12-11 | D00289C | | 6 | | GD01815 | AC.. | 2 | | 001-099 |
| 0316 | 22 | | GA | | 3-6 | 34-12-11 | GD01815 | AC.. | 2 | | D00289C | 6 | | | 115-199 |
| 0317 | 22 | | GA | | 5-3 | 34-12-11 | D00289C | | 4 | | SM00012 | | WI | | 001-099 |
| 0317 | 22 | | GA | | 5-3 | 34-12-11 | SM00012 | | | WI | D00289C | 4 | | | 115-199 |
| 0320 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | | G08 | | GD01808 | ST.. | 2 | | ALL |
| 0321 | 24 | | GK | | 3-3 | 34-22-16 | D00081D | | B12 | | D41073J | 35 | | | 001-099 |
| 0321 | 24 | | GK | | 3-3 | 34-22-16 | D41073J | | 35 | | D00081D | B12 | | | 115-199 |
| 0322 | 24 | | GK | | 3-7 | 34-22-16 | D41601J | | 48 | | D41073J | 37 | | | ALL |
| 0323 | 24 | | GK | | 3-7 | 34-22-16 | D41601J | | 49 | | D41073J | 36 | | | ALL |
| 0326 | 22 | | GA | | 3-6 | 34-61-13 | D00173B | | B13 | | GD01810 | ST.. | 2 | *2 | 001, 009 |
| 0326 | 22 | | GA | | 3-6 | 34-61-13 | D00173B | | B13 | | GD01810 | ST.. | 2 | | 002-003, 005, 010 |
| 0326 | 22 | | GA | | 3-6 | 34-61-13 | D00173B | | B13 | | GD01810 | ST.. | # | | 004, 006-008 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0326 | 22 | | GA | | 5-0 | 34-61-13 | D00173B | B13 | | | TB0201Z | 14 | BJ | | 011-099 |
| 0327 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | D07 | | | GD01808 | ST.. | # | | ALL |
| 0328 | 22 | | GA | | 2-11 | 22-15-12 | D41093J | 8 | | | SM00058 | | WI | | ALL |
| 0329 | 22 | | GA | | 3-1 | 22-15-12 | D00035A | F09 | | | SM00058 | | WI | | ALL |
| 0330 | 22 | | GA | | 2-11 | 22-15-12 | D41093J | 43 | | | SM00058 | | WI | | ALL |
| 0333 | 22 | | GA | | 3-10 | 32-42-12 | D41701J | 29 | | | D41810J | 1 | | | 115-199 |
| 0334 | 22 | | GA | | 2-8 | 32-42-12 | D41810J | 2 | | | SM00059 | | WI | | 115-199 |
| 0335 | 22 | | GA | | 2-11 | 32-42-12 | D41701J | 30 | | | SM00059 | | WI | | 115-199 |
| 0336 | 22 | | GA | | 3-10 | 32-42-12 | D41701J | 31 | | | D41810J | 3 | | | 115-199 |
| 0337 | 22 | | GA | | 2-11 | 32-42-12 | D41715J | 1 | | | D41810J | 4 | | | 115-199 |
| 0338 | 22 | | GA | | 3-0 | 32-42-12 | D41715J | 2 | | | SM00059 | | WI | | 115-199 |
| 0339 | 22 | | GA | | 2-11 | 32-42-12 | D41715J | 3 | | | D41810J | 5 | | | 115-199 |
| 0340 | 22 | | GA | | 2-11 | 32-42-12 | D41715J | 4 | | | D41810J | 6 | | | 115-199 |
| 0341 | 22 | | GA | | 2-11 | 32-42-12 | D41715J | 5 | | | D41810J | 7 | | | 115-199 |
| 0342 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | G09 | | | GD01808 | ST.. | 2 | | 001-099 |
| 0342 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | G09 | | | GD01808 | ST.. | # | | 115-199 |
| 0348 | 22 | | GA | | 3-4 | 30-32-11 | D42129J | 6 | | | D41093J | 9 | | | ALL |
| 0349 | 22 | | GA | | 3-4 | 30-32-11 | D42129J | 7 | | | D41093J | 10 | | | ALL |
| 0350 | 24 | | GK | | 2-4 | 31-51-34 | D41905J | 47 | | | SM00065 | | WI | | 009 |
| 0350 | 24 | | GK | | 2-4 | 31-51-34 | D41905J | 13 | | | SM00065 | | WI | | 115-199 |
| 0351 | 24 | | GK | | 3-2 | 34-22-17 | D00081A | F12 | | | SM00065 | | WI | | 009, 115-199 |
| 0353 | 22 | | GA | | 3-6 | 32-42-11 | D42011J | 36 | | | D41093J | 17 | | | ALL |
| 0354 | 20 | | GA | | 2-7 | 34-61-14 | D42183J | 12 | | | GD01813 | ST.. | 2 | | 001-008, 010-099, 115-199 |
| 0354 | 20 | | GA | | 2-7 | 34-61-14 | D42183J | 12 | | | GD01813 | ST.. | 2 | *1 | 009 |
| 0355 | 22 | | GA | | 3-1 | 22-14-11 | D00035B | K10 | | | SM00061 | | WI | | ALL |
| 0356 | 22 | | GA | | 2-7 | 22-14-11 | D42013J | 24 | | | SM00061 | | WI | | 001-099 |
| 0356 | 22 | | GA | | 2-7 | 22-14-11 | D42013J | 33 | | | SM00061 | | WI | | 115-199 |
| 0357 | 22 | | GA | | 3-1 | 22-14-11 | D00035B | K11 | | | SM00062 | | WI | | 001-099 |
| 0357 | 22 | | GA | | 3-1 | 22-14-11 | SM00062 | | WI | | D00035B | K11 | | | 115-199 |
| 0358 | 22 | | GA | | 3-1 | 22-14-11 | D00035B | K12 | | | SM00063 | | WI | | 001-099 |
| 0358 | 22 | | GA | | 3-1 | 22-14-11 | SM00063 | | WI | | D00035B | K12 | | | 115-199 |
| 0359 | 22 | | GA | | 2-7 | 22-14-11 | D42013J | 25 | | | SM00062 | | WI | | 001-099 |
| 0359 | 22 | | GA | | 2-7 | 22-14-11 | D42013J | 34 | | | SM00062 | | WI | | 115-199 |
| 0360 | 22 | | GA | | 2-7 | 22-14-11 | D42013J | 26 | | | SM00064 | | WI | | 001-099 |
| 0360 | 22 | | GA | | 2-7 | 22-14-11 | D42013J | 35 | | | SM00064 | | WI | | 115-199 |
| 0362 | 22 | | GA | | 3-1 | 22-14-11 | D00035B | J11 | | | SM00064 | | WI | | ALL |
| 0363 | 22 | | GA | | 6-7 | 34-12-12 | D00289B | D06 | | | D42013J | 31 | | | 115-199 |
| 0364 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | D07 | | | TB0201X | D087 | BJ | | 011-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | |
| 0364 | 22 | | GA | | 6-7 | 34-12-12 | D00289B | D07 | | | D42013J | 32 | | | 115-199 |
| 0366 | 22 | | GA | | 0-7 | 22-11-12 | D00035B | C08 | | | D00035B | E08 | | | 115-199 |
| 0368 | 22 | | GA | | 3-6 | 22-13-11 | D00035B | H02 | | | SM00026 | | WI | | ALL |
| 0369 | 22 | | GA | | 2-4 | 22-14-31 | D41905J | 29 | | | SM00017 | | WI | | 001-099 |
| 0369 | 22 | | GA | | 2-4 | 22-14-31 | D41905J | 29 | | | SM00017 | CAP | Y | | 115-199 |
| 0370 | 22 | | PA | | 0-7 | 22-11-12 | D00035B | D03 | | | D00035B | K04 | | | 115-199 |
| 0372 | 22 | | GA | | 3-2 | 34-22-16 | D00081B | D08 | | | SM00026 | | WI | | ALL |
| 0373 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | D09 | | | GD01808 | ST.. | # | | ALL |
| 0374 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | E11 | | | GD01808 | ST.. | # | | 001-006, 009-099, 115-199 |
| 0374 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | E11 | | | GD01808 | ST.. | 2 | | 007-008 |
| 0375 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | F11 | | | GD01809 | ST.. | 2 | | 001 |
| 0375 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | F11 | | | GD01809 | ST.. | # | | 002-008, 115-199 |
| 0375 | 22 | | GA | | 3-0 | 34-22-16 | D00081B | F11 | | | GD01809 | ST.. | 2 | | 009 |
| 0375 | 22 | | GA | | 3-0 | 34-22-16 | D00081B | F11 | | | GD01809 | ST.. | # | | 010-099 |
| 0376 | 22 | | GA | | 3-9 | 34-61-14 | D00173B | C15 | | | GD01808 | DC.. | # | | 001-010, 115-199 |
| 0376 | 22 | | GA | | 4-2 | 34-61-14 | D00173B | C15 | | | TB0201Z | 39 | BJ | | 011-099 |
| 0377 | 22 | | GA | | 3-9 | 34-61-14 | D00173B | D15 | | | GD01808 | DC.. | # | | 001-010, 115-199 |
| 0377 | 22 | | GA | | 3-3 | 34-61-14 | D00173B | D15 | | | TB0201Z | 91 | BJ | | 011-099 |
| 0378 | 22 | | GA | | 3-9 | 34-61-14 | D00173B | E15 | | | GD01808 | DC.. | # | | 001-010, 115-199 |
| 0378 | 22 | | GA | | 3-3 | 34-61-14 | D00173B | E15 | | | TB0201Z | 91 | BJ | | 011-099 |
| 0379 | 22 | | GA | | 3-9 | 34-61-14 | D00173B | F15 | | | GD01808 | DC.. | # | | 001-010, 115-199 |
| 0379 | 22 | | GA | | 3-3 | 34-61-14 | D00173B | F15 | | | TB0201Z | 91 | BJ | | 011-099 |
| 0380 | 24 | | GK | | 4-1 | 34-12-12 | D00289B | F07 | | | TB0201X | B085 | BJ | | 011-099 |
| 0380 | 24 | | GK | | 3-6 | 34-12-12 | D41339J | 24 | | | D00289B | F07 | | | 115-199 |
| 0381 | 22 | | GA | | 3-9 | 34-61-14 | D00173B | C11 | | | GD01808 | DC.. | # | | 001-010, 115-199 |
| 0381 | 22 | | GA | | 4-2 | 34-61-14 | D00173B | C11 | | | TB0201Z | 39 | BJ | | 011-099 |
| 0382 | 22 | | GA | | 3-9 | 34-61-14 | D00173B | G11 | | | GD01808 | DC.. | 2 | | 001-010, 115-199 |
| 0382 | 22 | | GA | | 4-2 | 34-61-14 | D00173B | G11 | | | TB0201Z | 40 | BJ | | 011-099 |
| 0383 | 22 | | GA | | 3-9 | 34-61-14 | D00173B | H11 | | | GD01808 | DC.. | # | | 001-010, 115-199 |
| 0383 | 22 | | GA | | 4-2 | 34-61-14 | D00173B | H11 | | | TB0201Z | 39 | BJ | | 011-099 |
| 0385 | 22 | | GA | | 5-0 | 34-61-13 | D00173B | B15 | | | TB0201Z | 13 | BJ | | 011-099 |
| 0386 | 22 | | GA | | 5-0 | 34-61-13 | D00173B | D13 | | | TB0201Z | 13 | BJ | | 011-099 |
| 0387 | 22 | | GA | | 3-6 | 34-61-13 | D00173B | C13 | | | GD01810 | ST.. | 2 | *2 | 001, 009 |
| 0387 | 22 | | GA | | 5-0 | 34-61-13 | D00173B | C13 | | | TB0201Z | 13 | BJ | | 011-099 |
| 0388 | 22 | | GA | | 3-7 | 34-61-15 | D42011J | 38 | | | D41905J | 38 | | | 001-099 |
| 0388 | 22 | | PA | | 3-7 | 34-61-15 | D41905J | 38 | | | TB0201B | C068 | 1A | | 115-199 |
| 0389 | 24 | | GK | | 4-11 | 73-21-12 | D41701J | 9 | | | D42230J | 11 | | | 001-099 |
| 0389 | 24 | | GK | | 4-11 | 73-21-12 | D41701J | 32 | | | D42230J | 11 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 0390 | 24 | GK | | | 4-11 | 73-21-12 | D41701J | 10 | | | D42230J | 12 | | | 001-099 |
| 0390 | 24 | GK | | | 4-11 | 73-21-12 | D41701J | 33 | | | D42230J | 12 | | | 115-199 |
| 0391 | 22 | GA | | | 3-0 | 22-14-31 | D41391J | 46 | | | SM00018 | | WI | | 001-099 |
| 0392 | 22 | GA | | | 6-1 | 34-12-11 | D00289C | 1 | | | D41429J | 2 | | | 001-099 |
| 0393 | 22 | GA | | | 4-6 | 22-14-11 | D00035A | F03 | | | D41339J | 26 | | | 001-099 |
| 0394 | 22 | GA | | | 2-6 | 22-14-11 | D41429J | 37 | | | SM00018 | | WI | | 001-099 |
| 0395 | 22 | GA | | | 3-6 | 22-14-11 | D00035A | E12 | | | SM00018 | | WI | | 001-099 |
| 0396 | 22 | GA | | | 4-6 | 22-14-11 | D00035B | K02 | | | D41339J | 20 | | | 001-099 |
| 0397 | 22 | GA | | | 3-3 | 22-11-12 | D00035C | 9 | | | D41429J | 26 | | | 001-099 |
| 0398 | 22 | GA | | | 2-9 | 22-11-22 | D41339J | 2 | | | SM00045 | | WI | | 001-099 |
| 0399 | 22 | GA | | | 2-7 | 22-14-31 | D41391J | 14 | | | SM00041 | | WI | | 001-099 |
| 0400 | 22 | GA | | | 3-1 | 22-14-11 | D00035B | G12 | | | SM00041 | | WI | | 001-099 |
| 0401 | 22 | GA | | | 3-1 | 22-14-11 | D41339J | 19 | | | SM00041 | | WI | | 001-099 |
| 0402 | 22 | GA | | | 3-1 | 22-14-11 | D00035A | G12 | | | SM00051 | | WI | | 001-099 |
| 0403 | 22 | GA | | | 2-7 | 22-14-11 | D41391J | 40 | | | SM00051 | | WI | | 001-099 |
| 0404 | 22 | GA | | | 2-7 | 22-14-31 | D41391J | 16 | | | SM00051 | | WI | | 001-099 |
| 0405 | 22 | GA | | | 3-0 | 22-14-31 | D41391J | 17 | | | SM00018 | | WI | | 001-099 |
| 0406 | 22 | GA | | | 3-3 | 22-15-12 | D00035A | K01 | | | D41391J | 22 | | | 001-099 |
| 0407 | 22 | GA | | | 4-3 | 22-15-12 | D00035A | K03 | | | D41745J | 4 | | | 001-099 |
| 0408 | 22 | GA | | | 3-9 | 22-14-21 | D41601J | 44 | | | SM00041 | | WI | | 001-099 |
| 0409 | 22 | GA | | | 3-0 | 22-14-21 | D41391J | 41 | | | SM00018 | | WI | | 001-099 |
| 0410 | 22 | GA | | | 2-7 | 22-14-21 | D41391J | 42 | | | SM00051 | | WI | | 001-099 |
| 0411 | 22 | GA | | | 4-6 | 22-41-11 | D00035B | C06 | | | D41339J | 16 | | | 001-099 |
| 0412 | 22 | GA | | | 2-7 | 22-14-11 | D41391J | 47 | | | SM00063 | | WI | | 001-099 |
| 0413 | 22 | GA | | | 6-1 | 22-41-13 | D00035B | F09 | | | D42065J | 12 | | | 001-099 |
| 0414 | 22 | GA | | | 5-5 | 22-41-13 | D00035B | F10 | | | D42011J | 7 | | | 001-099 |
| 0415 | 22 | GA | | | 3-3 | 22-15-12 | D00035A | G01 | | | D41391J | 36 | | | 001-099 |
| 0416 | 22 | GA | | | 4-6 | 22-15-12 | D00035A | E03 | | | D41339J | 14 | | | 001-099 |
| 0417 | 22 | GA | | | 3-0 | 22-11-32 | D41391J | 32 | | | SM00045 | | WI | | 001-099 |
| 0418 | 22 | GA | | | 0-7 | 22-11-12 | D00035B | C13 | | | D00035B | F04 | | | 002-008 |
| 0420 | 20 | GA | | | 1-6 | 34-22-18 | D41563J | | | CY | GD01810 | ST.. | 2 | | 001-099 |
| 0420 | 22 | GA | | | 4-7 | 34-61-13 | D00173B | C13 | | | GD01805 | ST.. | # | | 115-199 |
| 0429 | 22 | GA | | | 2-0 | 22-11-12 | D00035B | C13 | | | D00035B | F04 | | | 115-199 |
| 0437 | 22 | GA | | | 3-3 | 34-61-14 | D00173B | K15 | | | TB0201Z | 91 | BJ | | 011-099 |
| 0439 | 20 | GA | | | 3-8 | 34-45-01 | D41910J | 15 | | | D01583C | 1 | | | ALL |
| 0440 | 22 | GA | | | 3-7 | 34-45-01 | D01583C | 7 | | | GD01803 | AC.. | 2 | | ALL |
| 0441 | 22 | GA | | | 3-7 | 34-45-01 | D01583C | 8 | | | GD01803 | DC.. | 2 | | ALL |
| 0442 | 22 | GA | | | 3-7 | 34-45-01 | D01583C | 11 | | | GD01803 | DC.. | 2 | | ALL |
| 0443 | 22 | GA | | | 3-4 | 34-45-01 | D01583E | K05 | | | D41429J | 23 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0444 | 24 | | GK | | 3-1 | 34-45-01 | TB0201Y | A031 | BJ | | D01583E | E13 | | | 001-099 | |
| 0444 | 24 | | GK | | 4-9 | 34-45-01 | D42065J | 32 | | | D01583E | E13 | | | 115-199 | |
| 0446 | 22 | | GA | | 2-7 | 22-13-11 | D41905J | | | NA | GD01806 | ST.. | 2 | | 001-099 | |
| 0446 | 22 | | GA | | 3-0 | 22-13-11 | D43003J | | | NA | GD01806 | ST.. | 2 | | 115-199 | |
| 0448 | 22 | | GA | | 2-7 | 34-45-02 | D41905J | | | NB | GD01806 | ST.. | 2 | | 001-008, 010-099 | |
| 0448 | 22 | | GA | | 2-7 | 34-45-02 | D41905J | | | NB | GD01806 | ST.. | 2 | *2 | 009 | |
| 0448 | 22 | | GA | | 3-0 | 34-45-02 | D43003J | | | NB | GD01806 | ST.. | 2 | | 115-199 | |
| 0449 | 22 | | GA | | 2-7 | 34-45-02 | D41905J | | | NC | GD01806 | ST.. | 2 | | 001-008, 010-099 | |
| 0449 | 22 | | GA | | 2-7 | 34-45-02 | D41905J | | | NC | GD01806 | ST.. | 2 | *2 | 009 | |
| 0449 | 22 | | GA | | 3-0 | 34-45-02 | D43003J | | | NC | GD01806 | ST.. | 2 | | 115-199 | |
| 0450 | 22 | | GA | | 2-3 | 34-45-02 | D41339J | | | ND | GD01811 | ST.. | 2 | | ALL | |
| 0452 | 24 | | GK | | 4-4 | 34-45-01 | D42065J | 47 | | | TB0201Z | 22 | BJ | | 001-002 | |
| 0452 | 24 | | GK | | 4-4 | 34-45-01 | D42065J | 38 | | | TB0201Z | 22 | BJ | | 115-199 | |
| 0453 | 24 | | GK | | 4-4 | 34-45-01 | D42065J | 46 | | | TB0201Y | A031 | BJ | | 001-099 | |
| 0453 | 24 | | GK | | 4-4 | 34-45-01 | D42065J | 37 | | | TB0201Y | A031 | BJ | | 115-199 | |
| 0454 | 24 | | GK | | 2-8 | 34-45-01 | D42013J | 41 | | | TB0201Z | 22 | BJ | | 001-002, 115-199 | |
| 0455 | 24 | | GK | | 3-1 | 34-45-01 | TB0201Y | A032 | BJ | | D01583E | C14 | | | 001-099 | |
| 0455 | 24 | | GK | | 3-10 | 34-45-01 | D42013J | 45 | | | D01583E | C14 | | | 115-199 | |
| 0456 | 24 | | GK | | 2-9 | 34-45-01 | D42013J | 46 | | | TB0201Y | A032 | BJ | | ALL | |
| 0457 | 24 | | GK | | 2-8 | 34-45-01 | D41391J | 51 | | | TB0201Z | 22 | BJ | | 001-002, 115-199 | |
| 0457 | 24 | | GK | | 2-8 | 34-45-01 | D41391J | 51 | | | TB0201Y | A031 | BJ | | 003-099 | |
| 0458 | 24 | | GK | | 2-8 | 34-45-01 | D41391J | 52 | | | TB0201Y | A032 | BJ | | ALL | |
| 0459 | 24 | | GK | | 3-7 | 34-45-01 | D01583E | E07 | | | GD01803 | DC.. | 2 | | 001-002 | |
| 0459 | 22 | | GA | | 3-7 | 34-45-01 | D01583E | E07 | | | GD01803 | DC.. | 2 | | 003-099 | |
| 0459 | 24 | | GK | | 3-1 | 34-45-01 | D01583E | E07 | | | TB0201Y | A032 | BJ | | 115-199 | |
| 0460 | 24 | | GK | | 3-7 | 34-45-01 | TB0201Y | A032 | BJ | | D00081E | E11 | | | 001-099 | |
| 0460 | 24 | | GK | | 3-7 | 34-45-01 | TB0201Y | A032 | BJ | | D00081A | REF | VP | | 115-199 | |
| 0461 | 22 | | GA | | 3-7 | 34-45-01 | D43003J | 2 | | | D01583E | F13 | | | ALL | |
| 0462 | 24 | | GK | | 3-3 | 34-45-01 | D41339J | 27 | | | TB0201Z | 22 | BJ | | 001-002, 115-199 | |
| 0463 | 24 | | GK | | 3-3 | 34-45-01 | D41339J | 54 | | | TB0201Y | A031 | BJ | | ALL | |
| 0464 | 24 | | GK | | 3-7 | 34-45-01 | D01583E | J07 | | | GD01803 | DC.. | 2 | | 001-002 | |
| 0464 | 22 | | GA | | 3-7 | 34-45-01 | D01583E | J07 | | | GD01803 | DC.. | 2 | | 003-099 | |
| 0464 | 24 | | GK | | 3-1 | 34-45-01 | D01583E | J07 | | | TB0201Y | A031 | BJ | | 115-199 | |
| 0465 | 24 | | GK | | 3-1 | 34-45-01 | D01583E | K13 | | | TB0201Z | 22 | BJ | | 001-002, 115-199 | |
| 0466 | 24 | | GK | | 2-3 | 34-45-02 | D41429J | 24 | | | TB0201Z | 22 | BJ | | 001-002, 115-199 | |
| 0466 | 24 | | GK | | 3-4 | 34-45-02 | D41429J | 24 | | | D01583E | K13 | | | 003-099 | |
| 0468 | 24 | | GK | | 3-3 | 34-45-02 | D41905J | 13 | | | D01583F | B05 | | | 001, 003-099 | |
| 0468 | 22 | | GK | | 3-3 | 34-43-14 | D41238J | 55 | | | D01583F | B05 | | | 002 | |
| 0468 | 24 | | GK | | 3-7 | 34-45-02 | D43003J | 30 | | | D01583F | B05 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 0469 | 24 | | GK | | 3-3 | 34-45-02 | D41905J | | 14 | | D01583F | | C05 | | 001, 003-099 |
| 0469 | 24 | | GK | | 3-7 | 34-45-02 | D43003J | | 31 | | D01583F | | C05 | | 115-199 |
| 0470 | 24 | | GK | | 3-3 | 34-45-02 | D41905J | | 15 | | D01583F | | D05 | | 001, 003-099 |
| 0470 | 24 | | GK | | 3-7 | 34-45-02 | D43003J | | 32 | | D01583F | | D05 | | 115-199 |
| 0471 | 24 | | GK | | 3-3 | 34-45-02 | D41905J | | 11 | | D01583F | | A05 | | 001, 003-099 |
| 0471 | 24 | | GK | | 3-7 | 34-45-02 | D43003J | | 33 | | D01583F | | A05 | | 115-199 |
| 0472 | 22 | | GA | | 2-3 | 34-45-02 | D41339J | | | NE | GD01811 | ST.. | 2 | | ALL |
| 0473 | 22 | | GA | | 2-3 | 34-45-02 | D41339J | | | NF | GD01811 | ST.. | 2 | | 001-099 |
| 0473 | 22 | | GA | | 3-10 | 34-45-02 | D43003J | | | NF | GD01811 | ST.. | 2 | | 115-199 |
| 0474 | 22 | | GA | | 3-3 | 34-45-02 | D41429J | | 52 | | GD01809 | ST.. | 2 | | ALL |
| 0475 | 22 | | GA | | 2-10 | 34-45-02 | D41339J | | | NI | GD01814 | ST.. | 2 | | ALL |
| 0476 | 22 | | GA | | 2-9 | 34-45-01 | D42065J | | | NJ | GD01816 | ST.. | 2 | | 001-002, 115-199 |
| 0477 | 22 | | GA | | 2-10 | 34-45-01 | D42013J | | | NL | GD01805 | ST.. | 2 | | 001-002, 115-199 |
| 0478 | 22 | | GA | | 3-7 | 34-45-01 | D01583E | E01 | | | GD01803 | DC.. | 2 | | 115-199 |
| 0482 | 24 | | GK | | 0-7 | 34-45-02 | D01583E | H06 | | | SM00077 | | WI | | ALL |
| 0483 | 24 | | GK | | 0-7 | 34-45-02 | D01583E | J06 | | | SM00077 | | WI | | ALL |
| 0484 | 24 | | GK | | 0-7 | 34-45-02 | D01583E | K06 | | | SM00077 | | WI | | ALL |
| 0485 | 24 | | GK | | 0-7 | 34-45-02 | D01583F | B07 | | | SM00081 | | WI | | 001-099 |
| 0485 | 24 | | GK | | 0-7 | 34-45-02 | D01583F | B07 | | | D01583F | K07 | | | 115-199 |
| 0491 | 22 | | GA | | 0-7 | 22-11-12 | D00035B | A04 | | | D00035A | D04 | | | 001-008 |
| 0491 | 22 | | GA | | 0-7 | 22-11-12 | D00035A | D04 | | | D00035B | A04 | | | 115-199 |
| 0494 | 22 | | GA | | 3-7 | 34-22-16 | D00081A | C14 | | | TB0201Y | A035 | BJ | | ALL |
| 0495 | 22 | | GA | | 3-11 | 34-22-16 | D41601J | 52 | | | TB0201Y | A035 | BJ | | ALL |
| 0496 | 22 | | GA | | 3-7 | 34-22-16 | D00081A | K13 | | | TB0201Y | A035 | BJ | | ALL |
| 0497 | 22 | | GA | | 3-4 | 34-22-16 | D00081D | D12 | | | GD01810 | ST.. | 2 | | ALL |
| 0498 | 24 | | GK | | 3-7 | 34-22-17 | D00081A | A11 | | | D41563J | 55 | | | ALL |
| 0499 | 20 | | GA | | 2-8 | 34-22-19 | D41601J | | | KV | GD01814 | ST.. | 2 | | ALL |
| 0501 | 20 | | GA | | 2-6 | 34-22-19 | D41563J | | | KW | GD01813 | ST.. | 2 | | 001-008, 010-099, 115-199 |
| 0501 | 20 | | GA | | 2-6 | 34-22-19 | D41563J | | | KW | GD01813 | ST.. | 2 | *1 | 009 |
| 0505 | 22 | | GA | | 4-2 | 34-61-14 | D00173B | H15 | | | TB0201Z | 39 | BJ | | 011-099 |
| 0506 | 22 | | GA | | 4-2 | 34-61-14 | D00173B | J11 | | | TB0201Z | 39 | BJ | | 011-099 |
| 0512 | 22 | | GA | | 0-7 | 22-11-12 | D00035B | A12 | | | D00035B | B15 | | | 001-008, 115-199 |
| 0513 | 22 | | PA | | 3-0 | 34-61-15 | TB0201B | A068 | 1A | | SM00072 | | 9 | | 115-199 |
| 0514 | 22 | | PA | | 3-0 | 34-61-16 | TB0201E | A070 | 2 | | SM00072 | | 9 | | 115-199 |
| 0515 | 22 | | PA | | 3-0 | 34-61-16 | TB0201D | A069 | 2 | | SM00072 | | 9 | | 115-199 |
| 0523 | 22 | | GA | | 2-11 | 34-22-16 | D00081A | B10 | | | GD01809 | ST.. | # | | 003-008 |
| 0523 | 22 | | GA | | 3-0 | 34-22-16 | D00081A | B10 | | | GD01809 | ST.. | 2 | | 009-099 |
| 0524 | 22 | | GA | | 2-11 | 34-22-16 | D00081B | G03 | | | GD01809 | ST.. | # | | 003-008 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0524 | 22 | GA | | 3-0 | 34-22-16 | D00081B | G03 | | | | GD01809 | ST.. | 2 | | 009-099 |
| 0525 | 22 | GA | | 2-11 | 34-22-16 | D00081B | H03 | | | | GD01809 | ST.. | # | | 003-008 |
| 0525 | 22 | GA | | 3-0 | 34-22-16 | D00081B | H03 | | | | GD01809 | ST.. | 2 | | 009-099 |
| 0526 | 22 | GA | | 2-11 | 34-22-16 | D00081B | J04 | | | | GD01809 | ST.. | # | | 003-008 |
| 0526 | 22 | GA | | 3-0 | 34-22-16 | D00081B | J04 | | | | GD01809 | ST.. | 2 | | 009-099 |
| 0531 | 24 | GK | | 0-7 | 34-45-02 | D01583F | E08 | | | | SM00081 | | WI | | 001-099 |
| 0532 | 24 | GK | | 0-7 | 34-45-02 | D01583F | K07 | | | | SM00081 | | WI | | 001-099 |
| 0546 | 24 | GK | | 5-0 | 34-61-13 | D00173B | K13 | | | | TB0201Z | 13 | BJ | | 011-099 |
| 0550 | 22 | PA | | 4-0 | 34-61-13 | D00173B | K14 | | | | GD01805 | ST.. | 2 | | 115-199 |
| 0552 | 20 | GA | | 1-6 | 34-25-12 | D41238J | | | | MJ | GD01814 | ST.. | 2 | | 002 |
| 0553 | 20 | GA | | 1-6 | 34-25-12 | D41745J | | | | MS | GD01809 | ST.. | 2 | | 002 |
| 0554 | 22 | GA | | 6-0 | 34-25-12 | D42065J | 18 | | | | D00081D | F13 | | | 002 |
| 0555 | 24 | GK | | 0-7 | 34-45-02 | D01583F | A07 | | | | SM00081 | | WI | | 009-099 |
| 0556 | 24 | GK | | 0-7 | 34-45-02 | D01583F | C07 | | | | SM00081 | | WI | | 009-099 |
| 0557 | 22 | GA | | 3-0 | 34-22-16 | D00081B | B02 | | | | GD01809 | ST.. | 2 | | 009-099 |
| 0563 | 22 | GA | | 3-0 | 22-11-12 | D00035B | F11 | | | | D00035B | K09 | | | 001, 115-199 |
| 0569 | 22 | GA | | 3-4 | 34-22-16 | D00081B | H06 | | | | GD01806 | ST.. | 2 | *1 | 010-099 |
| 0575 | 22 | GA | | 2-11 | 34-22-16 | D00081B | D05 | | | | GD01809 | ST.. | 2 | | 001-008 |
| 0575 | 22 | GA | | 3-0 | 34-22-16 | D00081B | D05 | | | | GD01809 | ST.. | # | | 009 |
| 0575 | 22 | GA | | 3-0 | 34-22-16 | D00081B | D05 | | | | GD01809 | ST.. | 2 | | 010-099 |
| 0576 | 22 | GA | | 2-11 | 34-22-16 | D00081B | F06 | | | | GD01808 | ST.. | 2 | | 001-099 |
| 0577 | 22 | GA | | 2-11 | 34-22-16 | D00081B | K04 | | | | GD01808 | ST.. | 2 | | 001-099 |
| 0581 | 22 | GA | | 2-10 | 34-22-18 | D41601J | | | | LA | GD01812 | ST.. | 2 | | 115-199 |
| 0582 | 22 | GA | | 2-11 | 34-22-16 | D00081B | D12 | | | | GD01809 | ST.. | # | | 001-008 |
| 0582 | 22 | GA | | 3-0 | 34-22-16 | D00081B | D12 | | | | GD01809 | ST.. | # | | 009-099 |
| 0582 | 22 | GA | | 3-4 | 34-22-16 | D00081B | D12 | | | | GD01806 | ST.. | 2 | | 115-199 |
| 0583 | 22 | GA | | 3-4 | 34-22-16 | D00081B | E12 | | | | GD01806 | ST.. | # | | 115-199 |
| 0592 | 22 | GA | | 4-0 | 34-22-16 | D00081B | E06 | | | | GD01814 | ST.. | 2 | | 115-199 |
| 0596 | 22 | GA | | 3-4 | 34-22-16 | D00081B | G06 | | | | GD01806 | ST.. | 2 | *1 | 010-099 |
| 0596 | 22 | GA | | 4-0 | 34-22-16 | D00081B | D06 | | | | GD01814 | ST.. | 2 | | 115-199 |
| 0599 | 22 | GA | | 3-2 | 34-61-13 | D00173B | J15 | | | | GD01812 | ST.. | 2 | *1 | 001-008, 010 |
| 0599 | 22 | GA | | 3-2 | 34-61-13 | D00173B | J15 | | | | GD01812 | ST.. | # | | 009 |
| 0599 | 22 | GA | | 5-0 | 34-61-13 | D00173B | J15 | | | | TB0201Z | 14 | BJ | | 011-099 |
| 0615 | 22 | GA | | 1-10 | 34-61-14 | TB0201Z | 40 | BJ | | | GD01806 | DC.. | 2 | | 011-099 |
| 0616 | 22 | GA | | 2-9 | 34-61-14 | TB0201Z | 92 | BJ | | | GD01812 | DC.. | 2 | | 011-099 |
| 0617 | 22 | GA | | 1-8 | 34-61-13 | TB0201Z | 14 | BJ | | | GD01803 | DC.. | 2 | | 011-099 |
| 0618 | 24 | GK | | 4-1 | 34-12-12 | D00289B | E06 | | | | TB0201X | C085 | BJ | | 011-099 |
| 0619 | 24 | GK | | 4-1 | 34-12-12 | D00289B | F06 | | | | TB0201X | D085 | BJ | | 011-099 |
| 0622 | 22 | GA | | 0-7 | 22-11-12 | D00035B | J02 | | | | D00035B | J04 | | | 001-008 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 0623 | 22 | GA | | | 0-7 | 22-11-12 | D00035B | | B12 | | D00035B | | D15 | | 001-008, 115-199 |
| 0624 | 22 | GA | | | 4-1 | 34-12-12 | D00289B | | B01 | | TB0201X | | A087 | BJ | 011-099 |
| 0625 | 22 | GA | | | 4-1 | 34-12-12 | D00289B | | C01 | | TB0201X | | B087 | BJ | 011-099 |
| 0626 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | C13 | | TB0201X | | A001 | BJ | 009 |
| 0626 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | C13 | | TB0201X | | A002 | BJ | 010-099 |
| 0627 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | A12 | | TB0201X | | B002 | BJ | 009-099 |
| 0628 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | B12 | | TB0201X | | C002 | BJ | 009-099 |
| 0629 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | C12 | | TB0201X | | D001 | BJ | 009-099 |
| 0630 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | A13 | | TB0201X | | A003 | BJ | 009-099 |
| 0631 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | B13 | | TB0201X | | B003 | BJ | 009-099 |
| 0632 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | C11 | | TB0201X | | C003 | BJ | 009-099 |
| 0632 | 22 | PA | | | 0-7 | 22-11-12 | D00035B | | C11 | | D00035B | | J08 | | 115-199 |
| 0633 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | F11 | | TB0201X | | D004 | BJ | 009-099 |
| 0634 | 22 | GA | | | 2-11 | 22-11-13 | D00035B | | D12 | | TB0201X | | A017 | BJ | 009-099 |
| 0635 | 22 | GA | | | 2-11 | 22-11-13 | D00035B | | F12 | | TB0201X | | B017 | BJ | 009-099 |
| 0636 | 22 | GA | | | 2-11 | 22-11-13 | D00035B | | H12 | | TB0201X | | C017 | BJ | 009-099 |
| 0637 | 22 | GA | | | 2-11 | 22-11-13 | D00035B | | G13 | | TB0201X | | D017 | BJ | 009-099 |
| 0638 | 22 | GA | | | 2-11 | 22-11-13 | D00035B | | C10 | | TB0201X | | A019 | BJ | 009-099 |
| 0639 | 22 | GA | | | 2-0 | 22-11-13 | D00035B | | D03 | | TB0201X | | B019 | BJ | 009 |
| 0639 | 22 | GA | | | 2-11 | 22-11-13 | D00035B | | D03 | | TB0201X | | B020 | BJ | 010-099 |
| 0641 | 22 | GA | | | 2-11 | 22-11-13 | D00035B | | A03 | | TB0201X | | C020 | BJ | 009-099 |
| 0642 | 22 | GA | | | 2-11 | 22-11-13 | D00035B | | K13 | | TB0201X | | D020 | BJ | 009-099 |
| 0643 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | H13 | | TB0201X | | A043 | BJ | 009-099 |
| 0643 | 22 | PA | | | 0-7 | 22-11-12 | D00035B | | J14 | | D00035B | | H13 | | 115-199 |
| 0644 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | C08 | | TB0201X | | B043 | BJ | 009-099 |
| 0645 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | D04 | | TB0201X | | C043 | BJ | 009-099 |
| 0646 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | J02 | | TB0201X | | D044 | BJ | 009-099 |
| 0647 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | G10 | | TB0201X | | A045 | BJ | 009-099 |
| 0648 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | J10 | | TB0201X | | B045 | BJ | 009 |
| 0648 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | J10 | | TB0201X | | B045 | BJ | 010-099 |
| 0649 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | G01 | | TB0201X | | C045 | BJ | 009-099 |
| 0650 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | H01 | | TB0201X | | D045 | BJ | 009-099 |
| 0651 | 22 | GA | | | 3-8 | 22-11-13 | D00035B | | A04 | | TB0201Y | | C042 | BJ | 009-099 |
| 0652 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | F04 | | TB0201X | | A002 | BJ | 009-099 |
| 0653 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | B15 | | TB0201X | | B002 | BJ | 009-099 |
| 0654 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | D15 | | TB0201X | | C002 | BJ | 009-099 |
| 0655 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | E05 | | TB0201X | | D002 | BJ | 009-099 |
| 0657 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | A14 | | TB0201X | | A004 | BJ | 009-099 |
| 0658 | 22 | GA | | | 3-0 | 22-11-13 | D00035B | | B14 | | TB0201X | | B004 | BJ | 009-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0659 | 22 | | GA | | 3-0 | 22-11-13 | D00035B | J08 | | | TB0201X | C004 | BJ | | 009-099 |
| 0660 | 22 | | GA | | 3-0 | 22-11-13 | D00035B | K09 | | | TB0201X | D004 | BJ | | 009-099 |
| 0661 | 22 | | GA | | 2-11 | 22-11-13 | D00035B | D14 | | | TB0201X | A018 | BJ | | 009-099 |
| 0662 | 22 | | GA | | 2-11 | 22-11-13 | D00035B | K07 | | | TB0201X | B018 | BJ | | 009-099 |
| 0663 | 22 | | GA | | 2-11 | 22-11-13 | D00035B | J15 | | | TB0201X | C018 | BJ | | 009-099 |
| 0664 | 22 | | GA | | 2-11 | 22-11-13 | D00035B | H14 | | | TB0201X | D018 | BJ | | 009-099 |
| 0665 | 22 | | GA | | 2-11 | 22-11-13 | D00035B | C14 | | | TB0201X | A020 | BJ | | 009-099 |
| 0666 | 22 | | GA | | 2-11 | 22-11-13 | D00035B | K04 | | | TB0201X | B020 | BJ | | 009-099 |
| 0667 | 22 | | GA | | 2-11 | 22-11-13 | D00035B | E04 | | | TB0201X | C020 | BJ | | 009-099 |
| 0668 | 22 | | GA | | 2-11 | 22-11-13 | D00035B | K14 | | | TB0201X | D020 | BJ | | 009-099 |
| 0669 | 22 | | GA | | 3-8 | 22-11-13 | D00035B | J14 | | | TB0201X | A044 | BJ | | 009-099 |
| 0670 | 22 | | GA | | 3-8 | 22-11-13 | D00035B | E08 | | | TB0201X | B044 | BJ | | 009-099 |
| 0671 | 22 | | GA | | 3-8 | 22-11-13 | D00035B | H04 | | | TB0201X | C044 | BJ | | 009-099 |
| 0672 | 22 | | GA | | 3-8 | 22-11-13 | D00035B | J04 | | | TB0201X | D044 | BJ | | 009-099 |
| 0673 | 22 | | GA | | 3-8 | 22-11-13 | D00035A | G08 | | | TB0201X | A046 | BJ | | 009-099 |
| 0674 | 22 | | GA | | 3-8 | 22-11-13 | D00035A | E10 | | | TB0201X | B046 | BJ | | 009-099 |
| 0675 | 22 | | GA | | 3-8 | 22-11-13 | D00035A | G02 | | | TB0201X | C046 | BJ | | 009-099 |
| 0676 | 22 | | GA | | 3-8 | 22-11-13 | D00035A | H02 | | | TB0201X | D046 | BJ | | 009-099 |
| 0677 | 22 | | GA | | 3-8 | 22-11-13 | D00035A | D04 | | | TB0201Y | C042 | BJ | | 009-099 |
| 0678 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | D08 | | | TB0201X | A088 | BJ | | 011-099 |
| 0679 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | E05 | | | TB0201X | B088 | BJ | | 011-099 |
| 0680 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | D15 | | | TB0201X | C088 | BJ | | 011-099 |
| 0681 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | E15 | | | TB0201X | D088 | BJ | | 011-099 |
| 0682 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | F08 | | | TB0201X | A086 | BJ | | 011-099 |
| 0683 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | E08 | | | TB0201X | B086 | BJ | | 011-099 |
| 0685 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | K15 | | | TB0201X | D086 | BJ | | 011-099 |
| 0686 | 22 | | GA | | 3-5 | 34-22-28 | D42011J | | | LF | GD01809 | ST.. | 2 | | 115-199 |
| 0687 | 20 | | GA | | 2-9 | 34-12-12 | TB0201Z | 89 | BJ | | GD01812 | DC.. | 2 | | 011-099 |
| 0688 | 20 | | GA | | 2-9 | 34-12-12 | TB0201Z | 90 | BJ | | GD01812 | DC.. | 2 | | 011-099 |
| 0692 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | J15 | | | TB0201X | C086 | BJ | | 011-099 |
| 0705 | 20 | | GA | | 4-1 | 34-61-14 | D41595J | | | PB | GD01810 | ST.. | 2 | | 001-099 |
| 0705 | 20 | | PA | | 1-6 | 34-61-14 | D41595J | | | PB | GD01802 | ST.. | 2 | | 115-199 |
| 0706 | 22 | | PA | | 3-0 | 34-61-15 | D41905J | 28 | | | SM00071 | | 9 | | 115-199 |
| 0707 | 22 | | PA | | 2-1 | 34-61-15 | D41429J | 3 | | | SM00072 | | 9 | | 115-199 |
| 0708 | 22 | | PA | | 6-0 | 34-61-16 | D42013J | 53 | | | SM00038 | | 9 | | 115-199 |
| 0709 | 22 | | PA | | 1-6 | 34-61-16 | D41081J | | | QW | GD01815 | ST.. | 2 | | 115-199 |
| 0710 | 22 | | PA | | 5-0 | 34-61-16 | TB0201E | C070 | 2 | | D43023J | 1 | | | 115-199 |
| 0711 | 22 | | PA | | 5-0 | 34-61-16 | D43023J | 19 | | | SM00071 | | 9 | | 115-199 |
| 0712 | 22 | | PA | | 5-0 | 34-61-16 | TB0201D | C069 | 2 | | D43023J | 18 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0713 | 22 | | PA | | 2-11 | 34-61-25 | D41339J | | 17 | | TB0201Z | 52 | BJ | | 115-199 |
| 0714 | 22 | | PA | | 5-0 | 34-61-15 | D42011J | | 38 | | SM00071 | | 9 | | 115-199 |
| 0724 | 24 | | PK | | 5-3 | 34-61-18 | D42013J | | 54 | | D00173B | J09 | | | 115-199 |
| 0725 | 24 | | PK | | 3-4 | 34-61-18 | D42065J | | 17 | | D00173B | K09 | | | 115-199 |
| 0733 | 24 | | GK | | 2-10 | 34-22-19 | D00081D | | G12 | | TB0201Y | A065 | BJ | | 001-099 |
| 0734 | 24 | | GK | | 3-3 | 34-22-19 | D41429J | | 28 | | TB0201Y | A065 | BJ | | 001-099 |
| 0735 | 24 | | GK | | 3-3 | 34-22-39 | D41429J | | 25 | | TB0201Y | A065 | BJ | | 001-099 |
| 0736 | 24 | | GK | | 3-3 | 34-22-29 | D41429J | | 3 | | TB0201Y | A065 | BJ | | 001-099 |
| 0746 | 20 | | PA | | 4-0 | 34-61-14 | D41817J | | | QV | GD01814 | ST.. | 2 | | 115-199 |
| 0756 | 22 | | GA | | 3-10 | 34-12-12 | D00289B | | C15 | | GD01814 | ST.. | 2 | | 001-010, 115-199 |
| 0756 | 22 | | GA | | 4-1 | 34-12-12 | D00289B | | C15 | | TB0201Z | 89 | BJ | | 011-099 |
| 0810 | 22 | | GA | | 6-0 | 34-22-16 | D41601J | | 1 | | D00081A | H14 | | | 002 |
| 0811 | 22 | | GA | | 6-0 | 34-22-16 | D41601J | | 2 | | D00081A | K14 | | | 002 |
| 0813 | 22 | | GA | | 6-0 | 34-43-15 | D41817J | | 29 | | D41238J | 22 | | | 002 |
| 0815 | 20 | | GA | | 6-0 | 34-22-18 | D21001J | | | ON | GD01807 | ST.. | 2 | | 002 |
| 0817 | 22 | | GA | | 4-0 | 34-22-18 | D00081E | | H11 | | TB0201Y | C064 | BJ | | 002 |
| 0818 | 22 | | GA | | 5-0 | 34-22-18 | D41089J | | 51 | | TB0201Y | C064 | BJ | | 002 |
| 0819 | 20 | | GA | | 4-0 | 34-46-12 | D41429J | | | D1 | GD01804 | ST.. | 2 | | 002 |
| 0829 | 24 | | PK | | 6-0 | 34-61-16 | D43023J | | 2 | | SM00038 | | 9 | | 115-199 |
| 0830 | 24 | | PK | | 4-9 | 34-22-17 | D00081A | | G15 | | SM00038 | | 9 | | 115-199 |
| 0831 | 24 | | PK | | 4-9 | 34-22-37 | D41601J | | 42 | | SM00038 | | 9 | | 115-199 |
| 0832 | 22 | | GA | | 7-0 | 34-46-14 | D41817J | | 30 | | D01583F | D05 | | | 002 |
| 0881 | 22 | | GA | | 4-0 | 34-12-61 | D42175J | | 16 | | GD01804 | DC.. | 2 | *8 | ALL |
| 0882 | 22 | | GA | | 4-0 | 34-12-61 | D42175J | | 14 | | TB0201F | C021 | 2 | | ALL |
| 0883 | 22 | | GA | | 4-0 | 34-12-61 | D42175J | | 15 | | TB0201F | A021 | 2 | | ALL |
| 0884 | 22 | | GA | | 2-0 | 34-12-61 | TB0201F | | A021 | 2 | GD01804 | DC.. | 2 | *8 | ALL |
| 0886 | 22 | | GA | | 4-0 | 34-12-61 | D42175J | | 1 | | D42011J | 40 | | | ALL |
| 0887 | 22 | | GA | | 3-5 | 34-12-61 | D42175J | | 2 | | D42011J | 39 | | | ALL |
| 0888 | 22 | | GA | | 3-0 | 34-12-61 | D42175J | | 9 | | SM00013 | | WI | | ALL |
| 0889 | 22 | | GA | | 3-0 | 34-12-61 | D42175J | | 17 | | SM00013 | | WI | | ALL |
| 0890 | 22 | | GA | | 3-0 | 34-12-61 | D42175J | | 10 | | SM00011 | | WI | | ALL |
| 0891 | 20 | | GA | | 2-0 | 27-32-11 | TB0201Y | | | SB | GD01804 | ST.. | 2 | | ALL |
| 0892 | 20 | | GA | | 2-0 | 27-32-11 | TB0201Y | | | SA | GD01804 | ST.. | 2 | | ALL |
| 0894 | 20 | | GA | | 2-0 | 27-32-11 | TB0201Y | | | FK | GD01804 | ST.. | 2 | | ALL |
| 1002 | 22 | | GT | IK | 3-0 | 22-14-31 | D41391J | | 46 | | SM00018 | | WI | | 115-199 |
| 1002Z | | | | IK | 0-0 | 22-14-31 | D41391J | | DED | | SM00018 | DED | | | 115-199 |
| 1003 | 22 | | GT | IN | 6-1 | 34-12-11 | D00289C | | 1 | | D41429J | 32 | | | 115-199 |
| 1003Z | | | | IN | 0-0 | 34-12-11 | D00289C | | DED | | D41429J | DED | | | 115-199 |
| 1004 | 22 | | GT | IO | 4-6 | 22-14-11 | D41339J | | 26 | | D00035A | F03 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | | | | | |
|--------------|-----------------|--|-------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|--|--|--|--|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | | |
| W1171 | 286N1171 | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | | | | | |
| 1004Z | | | IO | 0-0 | 22-14-11 | D41339J | DED | | D00035A | DED | | | 115-199 | | | | | | |
| 1005 | 22 | GT | IP | 2-6 | 22-14-11 | D41429J | 37 | | SM00018 | | WI | | 115-199 | | | | | | |
| 1005Z | | | IP | 0-0 | 22-14-11 | D41429J | DED | | SM00018 | DED | | | 115-199 | | | | | | |
| 1006 | 22 | GT | IQ | 3-6 | 22-14-11 | D00035A | E12 | | SM00018 | | WI | | 115-199 | | | | | | |
| 1006Z | | | IQ | 0-0 | 22-14-11 | D00035A | DED | | SM00018 | DED | | | 115-199 | | | | | | |
| 1007 | 22 | GT | IR | 4-6 | 22-14-11 | D41339J | 20 | | D00035B | K02 | | | 115-199 | | | | | | |
| 1007Z | | | IR | 0-0 | 22-14-11 | D41339J | DED | | D00035B | DED | | | 115-199 | | | | | | |
| 1008 | 22 | GT | IS | 3-3 | 22-11-12 | D00035C | 9 | | D41429J | 26 | | | 115-199 | | | | | | |
| 1008Z | | | IS | 0-0 | 22-11-12 | D00035C | DED | | D41429J | DED | | | 115-199 | | | | | | |
| 1009 | 22 | GT | IT | 2-9 | 22-11-22 | D41339J | 2 | | SM00045 | | WI | | 115-199 | | | | | | |
| 1009Z | | | IT | 0-0 | 22-11-22 | D41339J | DED | | SM00045 | DED | | | 115-199 | | | | | | |
| 1010 | 22 | GT | IU | 2-7 | 22-14-31 | SM00041 | | WI | D41391J | 14 | | | 115-199 | | | | | | |
| 1010Z | | | IU | 0-0 | 22-14-31 | SM00041 | DED | | D41391J | DED | | | 115-199 | | | | | | |
| 1011 | 22 | GT | IV | 3-1 | 22-14-11 | D00035B | G12 | | SM00041 | | WI | | 115-199 | | | | | | |
| 1011Z | | | IV | 0-0 | 22-14-11 | D00035B | DED | | SM00041 | DED | | | 115-199 | | | | | | |
| 1012 | 22 | GT | IW | 3-1 | 22-14-11 | D41339J | 19 | | SM00041 | | WI | | 115-199 | | | | | | |
| 1012Z | | | IW | 0-0 | 22-14-11 | D41339J | DED | | SM00041 | DED | | | 115-199 | | | | | | |
| 1013 | 22 | GT | IX | 3-1 | 22-14-11 | D00035A | G12 | | SM00051 | | WI | | 115-199 | | | | | | |
| 1013Z | | | IX | 0-0 | 22-14-11 | D00035A | DED | | SM00051 | DED | | | 115-199 | | | | | | |
| 1014 | 22 | GT | IY | 2-7 | 22-14-11 | D41391J | 40 | | SM00051 | | WI | | 115-199 | | | | | | |
| 1014Z | | | IY | 0-0 | 22-14-11 | D41391J | DED | | SM00051 | DED | | | 115-199 | | | | | | |
| 1015 | 22 | GT | IZ | 2-7 | 22-14-31 | D41391J | 16 | | SM00051 | | WI | | 115-199 | | | | | | |
| 1015Z | | | IZ | 0-0 | 22-14-31 | D41391J | DED | | SM00051 | DED | | | 115-199 | | | | | | |
| 1016 | 22 | GT | JA | 3-0 | 22-14-31 | D41391J | 17 | | SM00018 | | WI | | 115-199 | | | | | | |
| 1016Z | | | JA | 0-0 | 22-14-31 | D41391J | DED | | SM00018 | DED | | | 115-199 | | | | | | |
| 1017 | 22 | GT | JB | 3-3 | 22-15-12 | D41391J | 22 | | D00035A | K01 | | | 115-199 | | | | | | |
| 1017Z | | | JB | 0-0 | 22-15-12 | D41391J | DED | | D00035A | DED | | | 115-199 | | | | | | |
| 1018 | 22 | GT | JC | 4-3 | 22-15-12 | D41745J | 4 | | D00035A | K03 | | | 115-199 | | | | | | |
| 1018Z | | | JC | 0-0 | 22-15-12 | D41745J | DED | | D00035A | DED | | | 115-199 | | | | | | |
| 1019 | 22 | GT | JD | 3-9 | 22-14-21 | D41601J | 44 | | SM00041 | | WI | | 115-199 | | | | | | |
| 1019Z | | | JD | 0-0 | 22-14-21 | D41601J | DED | | SM00041 | DED | | | 115-199 | | | | | | |
| 1020 | 22 | GT | JE | 3-0 | 22-14-21 | D41391J | 41 | | SM00018 | | WI | | 115-199 | | | | | | |
| 1020Z | | | JE | 0-0 | 22-14-21 | D41391J | DED | | SM00018 | DED | | | 115-199 | | | | | | |
| 1021 | 22 | GT | JF | 2-7 | 22-14-21 | SM00051 | | WI | D41391J | 42 | | | 115-199 | | | | | | |
| 1021Z | | | JF | 0-0 | 22-14-21 | SM00051 | DED | | D41391J | DED | | | 115-199 | | | | | | |
| 1022 | 22 | GT | KI | 4-6 | 22-41-11 | D00035B | C06 | | D41339J | 16 | | | 115-199 | | | | | | |
| 1022Z | | | KI | 0-0 | 22-41-11 | D00035B | DED | | D41339J | DED | | | 115-199 | | | | | | |
| 1025 | 22 | GT | JJ | 2-7 | 22-14-11 | D41391J | 47 | | SM00063 | | WI | | 115-199 | | | | | | |
| 1025Z | | | JJ | 0-0 | 22-14-11 | D41391J | DED | | SM00063 | DED | | | 115-199 | | | | | | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|-------------------------------------|-------|-------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 1026 | 22 | GT | JK | 6-1 | 22-41-13 | D00035B | F09 | | | | D42065J | 12 | | | 115-199 |
| 1026Z | | | JK | 0-0 | 22-41-13 | D00035B | DED | | | | D42065J | DED | | | 115-199 |
| 1027 | 22 | GT | JL | 5-5 | 22-41-13 | D00035B | F10 | | | | D42011J | 7 | | | 115-199 |
| 1027Z | | | JL | 0-0 | 22-41-13 | D00035B | DED | | | | D42011J | DED | | | 115-199 |
| 1028 | 22 | GT | JO | 3-3 | 22-15-12 | D41391J | 36 | | | | D00035A | G01 | | | 115-199 |
| 1028Z | | | JO | 0-0 | 22-15-12 | D41391J | DED | | | | D00035A | DED | | | 115-199 |
| 1029 | 22 | GT | JP | 4-6 | 22-15-12 | D41339J | 14 | | | | D00035A | E03 | | | 115-199 |
| 1029Z | | | JP | 0-0 | 22-15-12 | D41339J | DED | | | | D00035A | DED | | | 115-199 |
| 1033 | 24 | G1 | KG | 2-6 | 73-21-22 | D41339J | 34 | | | | D41715J | 6 | | | 115-199 |
| 1033Z | | | KG | 0-0 | 73-21-22 | D41339J | DED | | | | D41715J | DED | | | 115-199 |
| 1034 | 24 | G1 | KH | 2-6 | 73-21-22 | D41339J | 35 | | | | D41715J | 7 | | | 115-199 |
| 1034Z | | | KH | 0-0 | 73-21-22 | D41339J | DED | | | | D41715J | DED | | | 115-199 |
| 1239 | 22 | GT | HU | 3-0 | 22-11-32 | D41391J | 32 | | | | SM00045 | | WI | | 115-199 |
| 1239Z | | | HU | 0-0 | 22-11-32 | D41391J | DED | | | | SM00045 | DED | | | 115-199 |
| 2006B | 22 | GB | KC | 4-1 | 22-12-11 | D00035B | F13 | | | | D41905J | 37 | | | ALL |
| 2006R | 22 | GB | KC | 0-0 | 22-12-11 | D00035B | E13 | | | | D41905J | 36 | | | ALL |
| 2012B | 20 | GB | BR | 3-9 | 22-11-11 | D00035C | 11 | | | | TB0201Z | 62 | BJ | | ALL |
| 2012R | 20 | GB | BR | 0-0 | 22-11-11 | D00035C | 10 | | | | TB0201Z | 61 | BJ | | ALL |
| 2013B | 22 | GB | BT | 2-10 | 22-11-11 | D41606J | 14 | | | | TB0201Z | 62 | BJ | | 001-099 |
| 2013B | 22 | GB | BT | 2-10 | 22-11-11 | TB0201Z | 62 | BJ | | | D41606J | 14 | | | 115-199 |
| 2013R | 22 | GB | BT | 0-0 | 22-11-11 | D41606J | 15 | | | | TB0201Z | 61 | BJ | | 001-099 |
| 2013R | 22 | GB | BT | 0-0 | 22-11-11 | TB0201Z | 61 | BJ | | | D41606J | 15 | | | 115-199 |
| 2014B | 22 | GB | BU | 3-0 | 22-11-11 | D41691J | 5 | | | | TB0201Z | 62 | BJ | | 001-099 |
| 2014B | 22 | GB | BU | 3-0 | 22-11-11 | TB0201Z | 62 | BJ | | | D41691J | 5 | | | 115-199 |
| 2014R | 22 | GB | BU | 0-0 | 22-11-11 | D41691J | 6 | | | | TB0201Z | 61 | BJ | | 001-099 |
| 2014R | 22 | GB | BU | 0-0 | 22-11-11 | TB0201Z | 61 | BJ | | | D41691J | 6 | | | 115-199 |
| 2015B | 22 | GB | BV | 3-0 | 22-11-11 | D41691J | 7 | | | | TB0201Z | 62 | BJ | | 001-099 |
| 2015B | 22 | GB | BV | 3-0 | 22-11-11 | TB0201Z | 62 | BJ | | | D41691J | 7 | | | 115-199 |
| 2015R | 22 | GB | BV | 0-0 | 22-11-11 | D41691J | 8 | | | | TB0201Z | 61 | BJ | | 001-099 |
| 2015R | 22 | GB | BV | 0-0 | 22-11-11 | TB0201Z | 61 | BJ | | | D41691J | 8 | | | 115-199 |
| 2016B | 22 | GB | BS | 3-0 | 22-11-11 | D41691J | 35 | | | | TB0201Z | 62 | BJ | | 001-099 |
| 2016B | 22 | GB | BS | 3-0 | 22-11-11 | TB0201Z | 62 | BJ | | | D41691J | 35 | | | 115-199 |
| 2016R | 22 | GB | BS | 0-0 | 22-11-11 | D41691J | 34 | | | | TB0201Z | 61 | BJ | | 001-099 |
| 2016R | 22 | GB | BS | 0-0 | 22-11-11 | TB0201Z | 61 | BJ | | | D41691J | 34 | | | 115-199 |
| 2017B | 22 | GB | BZ | 2-9 | 22-12-11 | D00035B | D11 | | | | D41691J | 9 | | | ALL |
| 2017R | 22 | GB | BZ | 0-0 | 22-12-11 | D00035B | E11 | | | | D41691J | 10 | | | ALL |
| 2018B | 22 | GB | FY | 2-8 | 22-13-11 | D00035B | E06 | | | | D41606J | 5 | | | ALL |
| 2018R | 22 | GB | FY | 0-0 | 22-13-11 | D00035B | F06 | | | | D41606J | 6 | | | ALL |
| 2019B | 22 | GB | GB | 2-9 | 22-13-11 | D00035B | E07 | | | | D41691J | 11 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 22

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | |
| 2019R | 22 | GB | GB | | 0-0 | 22-13-11 | D00035B | F07 | | | D41691J | 12 | | | ALL |
| 2501T | 24 | BV | CK | | 3-3 | 34-22-14 | D00081E | A01 | | | D41073J | 1 | | | 001-099 |
| 2501T | 24 | BV | CK | | 3-3 | 34-22-14 | D41073J | 1 | | | D00081E | A01 | | | 115-199 |
| 2501W | 24 | BV | CK | | 0-0 | 34-22-14 | D00081E | B01 | | | D41073J | 2 | | | 001-099 |
| 2501W | 24 | BV | CK | | 0-0 | 34-22-14 | D41073J | 2 | | | D00081E | B01 | | | 115-199 |
| 2501Z | | | CK | | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 3 | | | 001-099 |
| 2501Z | | | CK | | 0-0 | 34-22-14 | D41073J | 3 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2502T | 24 | BV | CL | | 3-3 | 34-22-14 | D00081E | A02 | | | D41073J | 4 | | | 001-099 |
| 2502T | 24 | BV | CL | | 3-3 | 34-22-14 | D41073J | 4 | | | D00081E | A02 | | | 115-199 |
| 2502W | 24 | BV | CL | | 0-0 | 34-22-14 | D00081E | B02 | | | D41073J | 5 | | | 001-099 |
| 2502W | 24 | BV | CL | | 0-0 | 34-22-14 | D41073J | 5 | | | D00081E | B02 | | | 115-199 |
| 2502Z | | | CL | | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 6 | | | 001-099 |
| 2502Z | | | CL | | 0-0 | 34-22-14 | D41073J | 6 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2503T | 24 | BV | CM | | 3-3 | 34-22-14 | D00081E | A03 | | | D41073J | 7 | | | 001-099 |
| 2503T | 24 | BV | CM | | 3-3 | 34-22-14 | D41073J | 7 | | | D00081E | A03 | | | 115-199 |
| 2503W | 24 | BV | CM | | 0-0 | 34-22-14 | D00081E | B03 | | | D41073J | 8 | | | 001-099 |
| 2503W | 24 | BV | CM | | 0-0 | 34-22-14 | D41073J | 8 | | | D00081E | B03 | | | 115-199 |
| 2503Z | | | CM | | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 9 | | | 001-099 |
| 2503Z | | | CM | | 0-0 | 34-22-14 | D41073J | 9 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2504T | 24 | BV | CN | | 3-3 | 34-22-14 | D00081E | A04 | | | D41073J | 10 | | | 001-099 |
| 2504T | 24 | BV | CN | | 3-3 | 34-22-14 | D41073J | 10 | | | D00081E | A04 | | | 115-199 |
| 2504W | 24 | BV | CN | | 0-0 | 34-22-14 | D00081E | B04 | | | D41073J | 11 | | | 001-099 |
| 2504W | 24 | BV | CN | | 0-0 | 34-22-14 | D41073J | 11 | | | D00081E | B04 | | | 115-199 |
| 2504Z | | | CN | | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 12 | | | 001-099 |
| 2504Z | | | CN | | 0-0 | 34-22-14 | D41073J | 12 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2505T | 24 | BV | CO | | 3-3 | 34-22-14 | D00081E | A05 | | | D41073J | 13 | | | 001-099 |
| 2505T | 24 | BV | CO | | 3-3 | 34-22-14 | D41073J | 13 | | | D00081E | A05 | | | 115-199 |
| 2505W | 24 | BV | CO | | 0-0 | 34-22-14 | D00081E | B05 | | | D41073J | 14 | | | 001-099 |
| 2505W | 24 | BV | CO | | 0-0 | 34-22-14 | D41073J | 14 | | | D00081E | B05 | | | 115-199 |
| 2505Z | | | CO | | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 15 | | | 001-099 |
| 2505Z | | | CO | | 0-0 | 34-22-14 | D41073J | 15 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2506T | 24 | BV | CP | | 3-3 | 34-22-14 | D00081E | A06 | | | D41073J | 16 | | | 001-099 |
| 2506T | 24 | BV | CP | | 3-3 | 34-22-14 | D41073J | 16 | | | D00081E | A06 | | | 115-199 |
| 2506W | 24 | BV | CP | | 0-0 | 34-22-14 | D00081E | B06 | | | D41073J | 17 | | | 001-099 |
| 2506W | 24 | BV | CP | | 0-0 | 34-22-14 | D41073J | 17 | | | D00081E | B06 | | | 115-199 |
| 2506Z | | | CP | | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 18 | | | 001-099 |
| 2506Z | | | CP | | 0-0 | 34-22-14 | D41073J | 18 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2507T | 24 | BV | CQ | | 3-3 | 34-22-14 | D00081E | A07 | | | D41073J | 19 | | | 001-099 |
| 2507T | 24 | BV | CQ | | 3-3 | 34-22-14 | D41073J | 19 | | | D00081E | A07 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 23

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 2507W | 24 | | BV | CQ | 0-0 | 34-22-14 | D00081E | B07 | | | D41073J | 20 | | | 001-099 |
| 2507W | 24 | | BV | CQ | 0-0 | 34-22-14 | D41073J | 20 | | | D00081E | B07 | | | 115-199 |
| 2507Z | | | | CQ | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 21 | | | 001-099 |
| 2507Z | | | | CQ | 0-0 | 34-22-14 | D41073J | 21 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2508T | 24 | | BV | CR | 3-3 | 34-22-14 | D00081E | A08 | | | D41073J | 22 | | | 001-099 |
| 2508T | 24 | | BV | CR | 3-3 | 34-22-14 | D41073J | 22 | | | D00081E | A08 | | | 115-199 |
| 2508W | 24 | | BV | CR | 0-0 | 34-22-14 | D00081E | B08 | | | D41073J | 23 | | | 001-099 |
| 2508W | 24 | | BV | CR | 0-0 | 34-22-14 | D41073J | 23 | | | D00081E | B08 | | | 115-199 |
| 2508Z | | | | CR | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 24 | | | 001-099 |
| 2508Z | | | | CR | 0-0 | 34-22-14 | D41073J | 24 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2509T | 24 | | BV | CS | 3-3 | 34-22-14 | D00081E | A09 | | | D41073J | 25 | | | 001-099 |
| 2509T | 24 | | BV | CS | 3-3 | 34-22-14 | D41073J | 25 | | | D00081E | A09 | | | 115-199 |
| 2509W | 24 | | BV | CS | 0-0 | 34-22-14 | D00081E | B09 | | | D41073J | 26 | | | 001-099 |
| 2509W | 24 | | BV | CS | 0-0 | 34-22-14 | D41073J | 26 | | | D00081E | B09 | | | 115-199 |
| 2509Z | | | | CS | 0-0 | 34-22-14 | GD01819 | ST.. | 2 | | D41073J | 27 | | | 001-099 |
| 2509Z | | | | CS | 0-0 | 34-22-14 | D41073J | 27 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2510T | 24 | | BV | DL | 3-3 | 34-22-15 | D00081E | C01 | | | D41075J | 1 | | | 001-099 |
| 2510T | 24 | | BV | DL | 3-3 | 34-22-15 | D41075J | 1 | | | D00081E | C01 | | | 115-199 |
| 2510W | 24 | | BV | DL | 0-0 | 34-22-15 | D00081E | D01 | | | D41075J | 2 | | | 001-099 |
| 2510W | 24 | | BV | DL | 0-0 | 34-22-15 | D41075J | 2 | | | D00081E | D01 | | | 115-199 |
| 2510Z | | | | DL | 0-0 | 34-22-15 | GD01819 | ST.. | 2 | | D41075J | 3 | | | 001-099 |
| 2510Z | | | | DL | 0-0 | 34-22-15 | D41075J | 3 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2511T | 24 | | BV | DM | 3-3 | 34-22-15 | D00081E | C02 | | | D41075J | 4 | | | 001-099 |
| 2511T | 24 | | BV | DM | 3-3 | 34-22-15 | D41075J | 4 | | | D00081E | C02 | | | 115-199 |
| 2511W | 24 | | BV | DM | 0-0 | 34-22-15 | D00081E | D02 | | | D41075J | 5 | | | 001-099 |
| 2511W | 24 | | BV | DM | 0-0 | 34-22-15 | D41075J | 5 | | | D00081E | D02 | | | 115-199 |
| 2511Z | | | | DM | 0-0 | 34-22-15 | GD01819 | ST.. | 2 | | D41075J | 6 | | | 001-099 |
| 2511Z | | | | DM | 0-0 | 34-22-15 | D41075J | 6 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2512T | 24 | | BV | DN | 3-3 | 34-22-15 | D00081E | C03 | | | D41075J | 7 | | | 001-099 |
| 2512T | 24 | | BV | DN | 3-3 | 34-22-15 | D41075J | 7 | | | D00081E | C03 | | | 115-199 |
| 2512W | 24 | | BV | DN | 0-0 | 34-22-15 | D00081E | D03 | | | D41075J | 8 | | | 001-099 |
| 2512W | 24 | | BV | DN | 0-0 | 34-22-15 | D41075J | 8 | | | D00081E | D03 | | | 115-199 |
| 2512Z | | | | DN | 0-0 | 34-22-15 | GD01819 | ST.. | 2 | | D41075J | 9 | | | 001-099 |
| 2512Z | | | | DN | 0-0 | 34-22-15 | D41075J | 9 | | | GD01819 | ST.. | 2 | | 115-199 |
| 2513T | 24 | | BV | DO | 3-3 | 34-22-15 | D00081E | C04 | | | D41075J | 10 | | | 001-099 |
| 2513T | 24 | | BV | DO | 3-3 | 34-22-15 | D41075J | 10 | | | D00081E | C04 | | | 115-199 |
| 2513W | 24 | | BV | DO | 0-0 | 34-22-15 | D00081E | D04 | | | D41075J | 11 | | | 001-099 |
| 2513W | 24 | | BV | DO | 0-0 | 34-22-15 | D41075J | 11 | | | D00081E | D04 | | | 115-199 |
| 2513Z | | | | DO | 0-0 | 34-22-15 | GD01819 | ST.. | 2 | | D41075J | 12 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 24

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1171 | 286N1171 | | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 2513Z | | | | DO | 0-0 | 34-22-15 | D41075J | 12 | | | | GD01819 | ST.. | 2 | | 115-199 | |
| 2514T | 24 | BV | DP | | 3-3 | 34-22-15 | D00081E | C05 | | | | D41075J | 13 | | | 001-099 | |
| 2514T | 24 | BV | DP | | 3-3 | 34-22-15 | D41075J | 13 | | | | D00081E | C05 | | | 115-199 | |
| 2514W | 24 | BV | DP | | 0-0 | 34-22-15 | D00081E | D05 | | | | D41075J | 14 | | | 001-099 | |
| 2514W | 24 | BV | DP | | 0-0 | 34-22-15 | D41075J | 14 | | | | D00081E | D05 | | | 115-199 | |
| 2514Z | | | DP | | 0-0 | 34-22-15 | GD01819 | ST.. | 2 | | | D41075J | 15 | | | 001-099 | |
| 2514Z | | | DP | | 0-0 | 34-22-15 | D41075J | 15 | | | | GD01819 | ST.. | 2 | | 115-199 | |
| 2515T | 24 | BV | DQ | | 3-3 | 34-22-15 | D00081E | C06 | | | | D41075J | 16 | | | 001-099 | |
| 2515T | 24 | BV | DQ | | 3-3 | 34-22-15 | D41075J | 16 | | | | D00081E | C06 | | | 115-199 | |
| 2515W | 24 | BV | DQ | | 0-0 | 34-22-15 | D00081E | D06 | | | | D41075J | 17 | | | 001-099 | |
| 2515W | 24 | BV | DQ | | 0-0 | 34-22-15 | D41075J | 17 | | | | D00081E | D06 | | | 115-199 | |
| 2515Z | | | DQ | | 0-0 | 34-22-15 | GD01819 | ST.. | 2 | | | D41075J | 18 | | | 001-099 | |
| 2515Z | | | DQ | | 0-0 | 34-22-15 | D41075J | 18 | | | | GD01819 | ST.. | 2 | | 115-199 | |
| 2516T | 24 | BV | DR | | 3-3 | 34-22-15 | D00081E | C07 | | | | D41075J | 19 | | | 001-099 | |
| 2516T | 24 | BV | DR | | 3-3 | 34-22-15 | D41075J | 19 | | | | D00081E | C07 | | | 115-199 | |
| 2516W | 24 | BV | DR | | 0-0 | 34-22-15 | D41075J | 20 | | | | D00081E | D07 | | | ALL | |
| 2516Z | | | DR | | 0-0 | 34-22-15 | GD01819 | ST.. | 2 | | | D41075J | 21 | | | 001-099 | |
| 2516Z | | | DR | | 0-0 | 34-22-15 | D41075J | 21 | | | | GD01819 | ST.. | 2 | | 115-199 | |
| 2517T | 24 | BV | DS | | 3-3 | 34-22-15 | D00081E | C08 | | | | D41075J | 22 | | | 001-099 | |
| 2517T | 24 | BV | DS | | 3-3 | 34-22-15 | D41075J | 22 | | | | D00081E | C08 | | | 115-199 | |
| 2517W | 24 | BV | DS | | 0-0 | 34-22-15 | D00081E | D08 | | | | D41075J | 23 | | | 001-099 | |
| 2517W | 24 | BV | DS | | 0-0 | 34-22-15 | D41075J | 23 | | | | D00081E | D08 | | | 115-199 | |
| 2517Z | | | DS | | 0-0 | 34-22-15 | GD01818 | ST.. | 2 | | | D41075J | 24 | | | 001-099 | |
| 2517Z | | | DS | | 0-0 | 34-22-15 | D41075J | 24 | | | | GD01818 | ST.. | 2 | | 115-199 | |
| 2518T | 24 | BV | DT | | 3-3 | 34-22-15 | D00081E | C09 | | | | D41075J | 25 | | | 001-099 | |
| 2518T | 24 | BV | DT | | 3-3 | 34-22-15 | D41075J | 25 | | | | D00081E | C09 | | | 115-199 | |
| 2518W | 24 | BV | DT | | 0-0 | 34-22-15 | D00081E | D09 | | | | D41075J | 26 | | | 001-099 | |
| 2518W | 24 | BV | DT | | 0-0 | 34-22-15 | D41075J | 26 | | | | D00081E | D09 | | | 115-199 | |
| 2518Z | | | DT | | 0-0 | 34-22-15 | GD01818 | ST.. | 2 | | | D41075J | 27 | | | 001-099 | |
| 2518Z | | | DT | | 0-0 | 34-22-15 | D41075J | 27 | | | | GD01818 | ST.. | 2 | | 115-199 | |
| 2519T | 24 | BV | GJ | | 3-3 | 34-22-35 | D00081B | A07 | | | | D41085J | 1 | | | ALL | |
| 2519W | 24 | BV | GJ | | 0-0 | 34-22-35 | D00081B | B07 | | | | D41085J | 2 | | | ALL | |
| 2519Z | | | GJ | | 0-0 | 34-22-35 | GD01818 | ST.. | 2 | | | D41085J | 3 | | | ALL | |
| 2520T | 24 | BV | GK | | 3-3 | 34-22-35 | D00081B | A08 | | | | D41085J | 4 | | | ALL | |
| 2520W | 24 | BV | GK | | 0-0 | 34-22-35 | D00081B | B08 | | | | D41085J | 5 | | | ALL | |
| 2520Z | | | GK | | 0-0 | 34-22-35 | GD01818 | ST.. | 2 | | | D41085J | 6 | | | ALL | |
| 2521T | 24 | BV | GL | | 3-3 | 34-22-35 | D00081B | A09 | | | | D41085J | 7 | | | ALL | |
| 2521W | 24 | BV | GL | | 0-0 | 34-22-35 | D00081B | B09 | | | | D41085J | 8 | | | ALL | |
| 2521Z | | | GL | | 0-0 | 34-22-35 | GD01817 | ST.. | 2 | | | D41085J | 9 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 25

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 2522T | 24 | BV | GN | 3-3 | 34-22-35 | D00081B | A10 | | | | D41085J | 10 | | | ALL |
| 2522W | 24 | BV | GN | 0-0 | 34-22-35 | D00081B | B10 | | | | D41085J | 11 | | | ALL |
| 2522Z | | | GN | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 12 | | | ALL |
| 2523T | 24 | BV | GO | 3-3 | 34-22-35 | D00081B | A11 | | | | D41085J | 13 | | | ALL |
| 2523W | 24 | BV | GO | 0-0 | 34-22-35 | D00081B | B11 | | | | D41085J | 14 | | | ALL |
| 2523Z | | | GO | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 15 | | | ALL |
| 2524T | 24 | BV | GP | 3-3 | 34-22-35 | D00081B | A12 | | | | D41085J | 16 | | | ALL |
| 2524W | 24 | BV | GP | 0-0 | 34-22-35 | D00081B | B12 | | | | D41085J | 17 | | | ALL |
| 2524Z | | | GP | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 18 | | | ALL |
| 2525T | 24 | BV | GQ | 3-3 | 34-22-35 | D00081B | A13 | | | | D41085J | 19 | | | ALL |
| 2525W | 24 | BV | GQ | 0-0 | 34-22-35 | D00081B | B13 | | | | D41085J | 20 | | | ALL |
| 2525Z | | | GQ | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 21 | | | ALL |
| 2526T | 24 | BV | GR | 3-3 | 34-22-35 | D00081B | A14 | | | | D41085J | 22 | | | ALL |
| 2526W | 24 | BV | GR | 0-0 | 34-22-35 | D00081B | B14 | | | | D41085J | 23 | | | ALL |
| 2526Z | | | GR | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 24 | | | ALL |
| 2527T | 24 | BV | GS | 3-3 | 34-22-35 | D00081B | A15 | | | | D41085J | 25 | | | ALL |
| 2527W | 24 | BV | GS | 0-0 | 34-22-35 | D00081B | B15 | | | | D41085J | 26 | | | ALL |
| 2527Z | | | GS | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 27 | | | ALL |
| 2528T | 24 | BV | GT | 3-3 | 34-22-35 | D00081B | J07 | | | | D41085J | 28 | | | ALL |
| 2528W | 24 | BV | GT | 0-0 | 34-22-35 | D00081B | K07 | | | | D41085J | 29 | | | ALL |
| 2528Z | | | GT | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 30 | | | ALL |
| 2529T | 24 | BV | GV | 3-3 | 34-22-35 | D00081B | J08 | | | | D41085J | 31 | | | ALL |
| 2529W | 24 | BV | GV | 0-0 | 34-22-35 | D00081B | K08 | | | | D41085J | 32 | | | ALL |
| 2529Z | | | GV | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 33 | | | ALL |
| 2530T | 24 | BV | GU | 3-3 | 34-22-35 | D00081B | J09 | | | | D41085J | 34 | | | ALL |
| 2530W | 24 | BV | GU | 0-0 | 34-22-35 | D00081B | K09 | | | | D41085J | 35 | | | ALL |
| 2530Z | | | GU | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 36 | | | ALL |
| 2531T | 24 | BV | GW | 3-3 | 34-22-35 | D00081B | J10 | | | | D41085J | 37 | | | ALL |
| 2531W | 24 | BV | GW | 0-0 | 34-22-35 | D00081B | K10 | | | | D41085J | 38 | | | ALL |
| 2531Z | | | GW | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 39 | | | ALL |
| 2532T | 24 | BV | GX | 3-3 | 34-22-35 | D00081B | J11 | | | | D41085J | 40 | | | ALL |
| 2532W | 24 | BV | GX | 0-0 | 34-22-35 | D00081B | K11 | | | | D41085J | 41 | | | ALL |
| 2532Z | | | GX | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 42 | | | ALL |
| 2533T | 24 | BV | GY | 3-3 | 34-22-35 | D00081B | J12 | | | | D41085J | 43 | | | ALL |
| 2533W | 24 | BV | GY | 0-0 | 34-22-35 | D00081B | K12 | | | | D41085J | 44 | | | ALL |
| 2533Z | | | GY | 0-0 | 34-22-35 | GD01817 | ST.. | | 2 | | D41085J | 45 | | | ALL |
| 2534T | 24 | BV | GZ | 3-3 | 34-22-35 | D00081B | J13 | | | | D41085J | 46 | | | ALL |
| 2534W | 24 | BV | GZ | 0-0 | 34-22-35 | D00081B | K13 | | | | D41085J | 47 | | | ALL |
| 2534Z | | | GZ | 0-0 | 34-22-35 | GD01818 | ST.. | | 2 | | D41085J | 48 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 26

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 2535T | 24 | BV | HA | | 3-3 | 34-22-35 | D00081B | J14 | | | D41085J | 49 | | | ALL |
| 2535W | 24 | BV | HA | | 0-0 | 34-22-35 | D00081B | K14 | | | D41085J | 50 | | | ALL |
| 2535Z | | | HA | | 0-0 | 34-22-35 | GD01818 | ST.. | 2 | | D41085J | 51 | | | ALL |
| 2536T | 24 | BV | HB | | 3-3 | 34-22-35 | D00081B | J15 | | | D41085J | 52 | | | ALL |
| 2536W | 24 | BV | HB | | 0-0 | 34-22-35 | D00081B | K15 | | | D41085J | 53 | | | ALL |
| 2536Z | | | HB | | 0-0 | 34-22-35 | GD01818 | ST.. | 2 | | D41085J | 54 | | | ALL |
| 2537B | 22 | GU | ER | | 3-9 | 34-12-11 | D00289B | J08 | | | D42135J | 4 | | | ALL |
| 2537R | 22 | GU | ER | | 0-0 | 34-12-11 | D00289B | H08 | | | D42135J | 3 | | | ALL |
| 2537Z | | | ER | | 0-0 | 34-12-11 | D00289B | K08 | | | D42135J | 2 | | | ALL |
| 2539B | 24 | G2 | IB | | 5-0 | 73-21-12 | D41391J | 34 | | | D42230J | 4 | | | ALL |
| 2539R | 24 | G2 | IB | | 0-0 | 73-21-12 | D41391J | 33 | | | D42230J | 5 | | | ALL |
| 2539Z | | | IB | | 0-0 | 73-21-12 | D41391J | 35 | | | D42230J | 8 | | | ALL |
| 2540B | 24 | G2 | IC | | 4-9 | 73-21-12 | D42230J | 6 | | | TB0201Y | C016 | BJ | | ALL |
| 2540R | 24 | G2 | IC | | 0-0 | 73-21-12 | D42230J | 7 | | | TB0201Y | A016 | BJ | | ALL |
| 2540Z | | | IC | | 0-0 | 73-21-12 | D42230J | 3 | | | GD01803 | ST.. | 2 | *1 | 001-099 |
| 2540Z | | | IC | | 0-0 | 73-21-12 | D42230J | 3 | | | GD01803 | ST.. | 2 | | 115-199 |
| 2541B | 24 | G2 | ID | | 6-4 | 73-21-12 | D00289B | B06 | | | TB0201Y | C015 | BJ | | ALL |
| 2541R | 24 | G2 | ID | | 0-0 | 73-21-12 | D00289B | A06 | | | TB0201Y | A015 | BJ | | ALL |
| 2541Z | | | ID | | 0-0 | 73-21-12 | D00289B | DED | | | GD01803 | ST.. | 2 | *1 | 001-099 |
| 2541Z | | | ID | | 0-0 | 73-21-12 | D00289B | DED | | | GD01803 | ST.. | 2 | | 115-199 |
| 2542B | 24 | G2 | IE | | 2-8 | 73-21-22 | D41429J | 29 | | | TB0201Y | A041 | BJ | | ALL |
| 2542R | 24 | G2 | IE | | 0-0 | 73-21-22 | D41429J | 30 | | | TB0201Y | A042 | BJ | | ALL |
| 2542Z | | | IE | | 0-0 | 73-21-22 | D41429J | 31 | | | GD01806 | ST.. | 2 | | ALL |
| 3001B | 24 | GM | EV | | 3-9 | 34-12-11 | D42065J | 10 | | | D00289B | J12 | | | ALL |
| 3001R | 24 | GM | EV | | 0-0 | 34-12-11 | D42065J | 9 | | | D00289B | H12 | | | ALL |
| 3001Y | 24 | GM | EV | | 0-0 | 34-12-11 | D42065J | 11 | | | D00289B | K12 | | | ALL |
| 3002B | 24 | GM | ES | | 3-8 | 34-12-11 | SM00067 | | WI | | D42011J | 20 | | | 001-099 |
| 3002B | 24 | GM | ES | | 3-0 | 34-12-11 | D42011J | 20 | | | D00289B | J10 | | | 115-199 |
| 3002R | 24 | GM | ES | | 0-0 | 34-12-11 | SM00066 | | WI | | D42011J | 19 | | | 001-099 |
| 3002R | 24 | GM | ES | | 0-0 | 34-12-11 | D42011J | 19 | | | D00289B | H10 | | | 115-199 |
| 3002Y | 24 | GM | ES | | 0-0 | 34-12-11 | SM00068 | | WI | | D42011J | 21 | | | 001-099 |
| 3002Y | 24 | GM | ES | | 0-0 | 34-12-11 | D42011J | 21 | | | D00289B | K10 | | | 115-199 |
| 3003B | 24 | GM | ET | | 3-0 | 34-12-11 | D42011J | 11 | | | D00289B | J11 | | | 115-199 |
| 3003R | 24 | GM | ET | | 0-0 | 34-12-11 | D42011J | 10 | | | D00289B | H11 | | | 115-199 |
| 3003Y | 24 | GM | ET | | 0-0 | 34-12-11 | D42011J | 12 | | | D00289B | K11 | | | 115-199 |
| 3004B | 24 | GM | EU | | 3-6 | 34-12-11 | D00289B | J04 | | | D42129J | 10 | | | 001-099 |
| 3004B | 24 | GM | EU | | 3-6 | 34-12-11 | D42129J | 10 | | | D00289B | J04 | | | 115-199 |
| 3004R | 24 | GM | EU | | 0-0 | 34-12-11 | D00289B | H04 | | | D42129J | 11 | | | 001-099 |
| 3004R | 24 | GM | EU | | 0-0 | 34-12-11 | D42129J | 11 | | | D00289B | H04 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 27

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|-------------------------------------|---------|----------|---------|-------|------|------|--------|---------|------|-------------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 3004Y | 24 | GM | EU | | 0-0 | 34-12-11 | D00289B | K04 | | | | D42129J | 12 | | | 001-099 |
| 3004Y | 24 | GM | EU | | 0-0 | 34-12-11 | D42129J | 12 | | | | D00289B | K04 | | | 115-199 |
| 3005B | 24 | GM | EQ | | 3-6 | 34-12-11 | D00289B | J02 | | | | D42129J | 4 | | | 001-099 |
| 3005B | 24 | GM | EQ | | 3-6 | 34-12-11 | D42129J | 4 | | | | D00289B | J02 | | | 115-199 |
| 3005R | 24 | GM | EQ | | 0-0 | 34-12-11 | D00289B | H02 | | | | D42129J | 3 | | | 001-099 |
| 3005R | 24 | GM | EQ | | 0-0 | 34-12-11 | D42129J | 3 | | | | D00289B | H02 | | | 115-199 |
| 3005Y | 24 | GM | EQ | | 0-0 | 34-12-11 | D00289B | K02 | | | | D42129J | 5 | | | 001-099 |
| 3005Y | 24 | GM | EQ | | 0-0 | 34-12-11 | D42129J | 5 | | | | D00289B | K02 | | | 115-199 |
| 3006B | 22 | GC | CA | | 2-9 | 22-12-11 | D00035B | H10 | | | | D41691J | 16 | | | ALL |
| 3006R | 22 | GC | CA | | 0-0 | 22-12-11 | D00035B | J09 | | | | D41691J | 4 | | | ALL |
| 3006Y | 22 | GC | CA | | 0-0 | 22-12-11 | D00035B | H09 | | | | D41691J | 18 | | | ALL |
| 3007B | 22 | GC | CB | | 2-9 | 22-12-11 | D00035A | H10 | | | | D41691J | 13 | | | ALL |
| 3007R | 22 | GC | CB | | 0-0 | 22-12-11 | D00035A | J09 | | | | D41691J | 14 | | | ALL |
| 3007Y | 22 | GC | CB | | 0-0 | 22-12-11 | D00035A | H09 | | | | D41691J | 15 | | | ALL |
| 3008B | 22 | GC | CD | | 2-9 | 22-12-11 | D00035B | D05 | | | | D41691J | 37 | | | ALL |
| 3008R | 22 | GC | CD | | 0-0 | 22-12-11 | D00035B | C05 | | | | D41691J | 36 | | | ALL |
| 3008Y | 22 | GC | CD | | 0-0 | 22-12-11 | D00035B | D06 | | | | D41691J | 38 | | | ALL |
| 3009B | 22 | GC | FZ | | 2-8 | 22-13-11 | D00035B | K06 | | | | D41606J | 7 | | | ALL |
| 3009R | 22 | GC | FZ | | 0-0 | 22-13-11 | D00035B | J05 | | | | D41606J | 8 | | | ALL |
| 3009Y | 22 | GC | FZ | | 0-0 | 22-13-11 | D00035B | K05 | | | | D41606J | 9 | | | ALL |
| 3010B | 22 | GC | GA | | 2-8 | 22-13-11 | D00035A | K06 | | | | D41606J | 10 | | | ALL |
| 3010R | 22 | GC | GA | | 0-0 | 22-13-11 | D00035A | J05 | | | | D41606J | 11 | | | ALL |
| 3010Y | 22 | GC | GA | | 0-0 | 22-13-11 | D00035A | K05 | | | | D41606J | 12 | | | ALL |
| 3011B | 22 | GC | GC | | 2-9 | 22-13-11 | D00035B | J06 | | | | D41691J | 22 | | | ALL |
| 3011R | 22 | GC | GC | | 0-0 | 22-13-11 | D00035B | H06 | | | | D41691J | 23 | | | ALL |
| 3011Y | 22 | GC | GC | | 0-0 | 22-13-11 | D00035B | H05 | | | | D41691J | 24 | | | ALL |
| 3012B | 22 | GC | GD | | 2-9 | 22-13-11 | D00035A | J06 | | | | D41691J | 19 | | | ALL |
| 3012R | 22 | GC | GD | | 0-0 | 22-13-11 | D00035A | H06 | | | | D41691J | 20 | | | ALL |
| 3012Y | 22 | GC | GD | | 0-0 | 22-13-11 | D00035A | H05 | | | | D41691J | 21 | | | ALL |
| 3020B | 24 | GM | JU | | 4-10 | 34-12-11 | D00289B | J10 | | | | SM00067 | | WI | | 001-099 |
| 3020R | 24 | GM | JU | | 0-0 | 34-12-11 | D00289B | H10 | | | | SM00066 | | WI | | 001-099 |
| 3020Y | 24 | GM | JU | | 0-0 | 34-12-11 | D00289B | K10 | | | | SM00068 | | WI | | 001-099 |
| 3021B | 24 | GM | JV | | 4-10 | 34-12-11 | D00289B | J11 | | | | SM00067 | | WI | | 001-099 |
| 3021R | 24 | GM | JV | | 0-0 | 34-12-11 | D00289B | H11 | | | | SM00066 | | WI | | 001-099 |
| 3021Y | 24 | GM | JV | | 0-0 | 34-12-11 | D00289B | K11 | | | | SM00068 | | WI | | 001-099 |
| 5001B | 24 | G2 | CI | | 2-9 | 34-22-14 | D41073J | 31 | | | | TB0201Z | 53 | BJ | | ALL |
| 5001R | 24 | G2 | CI | | 0-0 | 34-22-14 | D41073J | 32 | | | | TB0201Z | 54 | BJ | | ALL |
| 5001Z | | | CI | | 0-0 | 34-22-14 | D41073J | 33 | | | | GD01807 | ST.. | 2 | *1 | 001-099 |
| 5001Z | | | CI | | 0-0 | 34-22-14 | GD01807 | ST.. | 2 | | | D41073J | 33 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 28

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | |
| 5002B | 24 | G2 | CJ | | 3-3 | 34-22-14 | D00081A | F05 | | | TB0201Z | 53 | BJ | | ALL |
| 5002R | 24 | G2 | CJ | | 0-0 | 34-22-14 | D00081A | E05 | | | TB0201Z | 54 | BJ | | ALL |
| 5002Z | | | CJ | | 0-0 | 34-22-14 | D00081A | DED | | | GD01807 | ST.. | 2 | *1 | 001-099 |
| 5002Z | | | CJ | | 0-0 | 34-22-14 | GD01807 | ST.. | 2 | | D00081A | DED | | | 115-199 |
| 5003B | 24 | G2 | DA | | 2-10 | 34-22-19 | D00081A | K03 | | | TB0201Z | 75 | BJ | | 001-099 |
| 5003B | 24 | G2 | DA | | 2-10 | 34-22-19 | D00081A | K03 | | | TB0201Y | C075 | BJ | | 115-199 |
| 5003R | 24 | G2 | DA | | 0-0 | 34-22-19 | D00081A | J03 | | | TB0201Z | 76 | BJ | | 001-099 |
| 5003R | 24 | G2 | DA | | 0-0 | 34-22-19 | D00081A | J03 | | | TB0201Y | C076 | BJ | | 115-199 |
| 5003Z | | | DA | | 0-0 | 34-22-19 | D00081A | DED | | | GD01810 | ST.. | 2 | *3 | 001 |
| 5003Z | | | DA | | 0-0 | 34-22-19 | D00081A | DED | | | GD01810 | ST.. | 2 | | 002-099, 115-199 |
| 5004B | 24 | G2 | DB | | 2-8 | 34-22-19 | D41089J | 54 | | | TB0201Z | 75 | BJ | | 001-099 |
| 5004B | 24 | G2 | DB | | 3-5 | 34-22-19 | D41831J | 10 | | | TB0201Y | C075 | BJ | | 115-199 |
| 5004R | 24 | G2 | DB | | 0-0 | 34-22-19 | D41089J | 53 | | | TB0201Z | 76 | BJ | | 001-099 |
| 5004R | 24 | G2 | DB | | 0-0 | 34-22-19 | D41831J | 9 | | | TB0201Y | C076 | BJ | | 115-199 |
| 5004Z | | | DB | | 0-0 | 34-22-19 | D41089J | 55 | | | GD01810 | ST.. | 2 | *3 | 001 |
| 5004Z | | | DB | | 0-0 | 34-22-19 | D41089J | 55 | | | GD01810 | ST.. | 2 | | 002-099 |
| 5004Z | | | DB | | 0-0 | 34-22-19 | D41831J | 11 | | | GD01810 | ST.. | 2 | | 115-199 |
| 5005B | 24 | G2 | DC | | 2-9 | 34-22-19 | D00081A | H02 | | | TB0201Z | 73 | BJ | | 001-099 |
| 5005B | 24 | G2 | DC | | 2-9 | 34-22-19 | D00081A | H02 | | | TB0201Y | A073 | BJ | | 115-199 |
| 5005R | 24 | G2 | DC | | 0-0 | 34-22-19 | D00081A | G02 | | | TB0201Z | 74 | BJ | | 001-099 |
| 5005R | 24 | G2 | DC | | 0-0 | 34-22-19 | D00081A | G02 | | | TB0201Y | A074 | BJ | | 115-199 |
| 5005Z | | | DC | | 0-0 | 34-22-19 | D00081A | DED | | | GD01810 | ST.. | 2 | *4 | 001 |
| 5005Z | | | DC | | 0-0 | 34-22-19 | D00081A | DED | | | GD01810 | ST.. | 2 | | 002-099, 115-199 |
| 5006B | 24 | G2 | DD | | 2-7 | 34-22-19 | D41089J | 27 | | | TB0201Z | 73 | BJ | | 001-099 |
| 5006B | 24 | G2 | DD | | 2-7 | 34-22-19 | D41089J | 27 | | | TB0201Y | A073 | BJ | | 115-199 |
| 5006R | 24 | G2 | DD | | 0-0 | 34-22-19 | D41089J | 26 | | | TB0201Z | 74 | BJ | | 001-099 |
| 5006R | 24 | G2 | DD | | 0-0 | 34-22-19 | D41089J | 26 | | | TB0201Y | A074 | BJ | | 115-199 |
| 5006Z | | | DD | | 0-0 | 34-22-19 | D41089J | 28 | | | GD01810 | ST.. | 2 | *4 | 001 |
| 5006Z | | | DD | | 0-0 | 34-22-19 | D41089J | 28 | | | GD01810 | ST.. | 2 | | 002-099, 115-199 |
| 5007B | 24 | G2 | DE | | 4-1 | 34-22-19 | D00081A | K01 | | | TB0201Z | 9 | BJ | | ALL |
| 5007R | 24 | G2 | DE | | 0-0 | 34-22-19 | D00081A | J01 | | | TB0201Z | 10 | BJ | | ALL |
| 5007Z | | | DE | | 0-0 | 34-22-19 | D00081A | DED | | | GD01802 | ST.. | 2 | | ALL |
| 5008B | 24 | G2 | DF | | 3-3 | 34-22-19 | D00081A | D04 | | | TB0201Z | 55 | BJ | | ALL |
| 5008R | 24 | G2 | DF | | 0-0 | 34-22-19 | D00081A | C04 | | | TB0201Z | 56 | BJ | | ALL |
| 5008Z | | | DF | | 0-0 | 34-22-19 | D00081A | DED | | | GD01808 | ST.. | 2 | | ALL |
| 5009B | 24 | G2 | DG | | 2-11 | 34-31-11 | D43003J | 21 | | | TB0201Z | 55 | BJ | | ALL |
| 5009R | 24 | G2 | DG | | 0-0 | 34-31-11 | D43003J | 20 | | | TB0201Z | 56 | BJ | | ALL |
| 5009Z | | | DG | | 0-0 | 34-31-11 | D43003J | 22 | | | GD01808 | ST.. | 2 | | ALL |
| 5010B | 24 | G2 | DH | | 3-7 | 34-22-19 | D00081A | K05 | | | D41563J | 39 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 29

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5010R | 24 | G2 | DH | | 0-0 | 34-22-19 | D00081A | J05 | | | D41563J | 38 | | | ALL |
| 5010Z | | | DH | | 0-0 | 34-22-19 | D00081A | DED | | | D41563J | | DH | | ALL |
| 5011B | 24 | G2 | DI | | 3-3 | 34-22-19 | D00081B | H04 | | | TB0201Z | 47 | BJ | | ALL |
| 5011R | 24 | G2 | DI | | 0-0 | 34-22-19 | D00081B | G04 | | | TB0201Z | 48 | BJ | | ALL |
| 5011Z | | | DI | | 0-0 | 34-22-19 | D00081B | DED | | | GD01807 | ST.. | 2 | | ALL |
| 5012B | 24 | G2 | DJ | | 3-2 | 34-33-11 | D41089J | 30 | | | TB0201Z | 47 | BJ | | ALL |
| 5012R | 24 | G2 | DJ | | 0-0 | 34-33-11 | D41089J | 29 | | | TB0201Z | 48 | BJ | | ALL |
| 5012Z | | | DJ | | 0-0 | 34-33-11 | D41089J | 31 | | | GD01807 | ST.. | 2 | | ALL |
| 5013B | 24 | G2 | DK | | 3-4 | 34-22-28 | D41563J | 42 | | | TB0201Z | 49 | BJ | | 001-099 |
| 5013R | 24 | G2 | DK | | 0-0 | 34-22-28 | D41563J | 41 | | | TB0201Z | 50 | BJ | | 001-099 |
| 5013Z | | | DK | | 0-0 | 34-22-28 | D41563J | 43 | | | GD01807 | ST.. | 2 | | 001-099 |
| 5014B | 24 | G2 | CT | | 3-3 | 34-22-18 | D00081A | B03 | | | TB0201Z | 49 | BJ | | ALL |
| 5014R | 24 | G2 | CT | | 0-0 | 34-22-18 | D00081A | A03 | | | TB0201Z | 50 | BJ | | ALL |
| 5014Z | | | CT | | 0-0 | 34-22-18 | D00081A | DED | | | GD01807 | ST.. | 2 | | 001-099 |
| 5014Z | | | CT | | 0-0 | 34-22-18 | GD01807 | ST.. | 2 | | D00081A | DED | | | 115-199 |
| 5015B | 24 | G2 | CU | | 4-2 | 34-61-15 | D00173A | B11 | | | TB0201Z | 49 | BJ | | ALL |
| 5015R | 24 | G2 | CU | | 0-0 | 34-61-15 | D00173A | A11 | | | TB0201Z | 50 | BJ | | ALL |
| 5015Z | | | CU | | 0-0 | 34-61-15 | D00173A | DED | | | GD01807 | ST.. | 2 | | 001-099 |
| 5015Z | | | CU | | 0-0 | 34-61-15 | GD01807 | ST.. | 2 | | D00173A | DED | | | 115-199 |
| 5016B | 24 | G2 | CV | | 2-6 | 34-43-11 | D41061J | 9 | | | TB0201Z | 53 | BJ | | 001, 003-099, 115-199 |
| 5016R | 24 | G2 | CV | | 0-0 | 34-43-11 | D41061J | 8 | | | TB0201Z | 54 | BJ | | 001, 003-099, 115-199 |
| 5016Z | | | CV | | 0-0 | 34-43-11 | D41061J | 7 | | | GD01807 | ST.. | 2 | | 001, 003-099 |
| 5016Z | | | CV | | 0-0 | 34-43-11 | GD01807 | ST.. | 2 | | D41061J | 7 | | | 115-199 |
| 5017B | 24 | G2 | CW | | 3-10 | 34-22-18 | D00081D | B03 | | | D41601J | 32 | | | 001-099 |
| 5017R | 24 | G2 | CW | | 0-0 | 34-22-18 | D00081D | A03 | | | D41601J | 31 | | | 001-099 |
| 5017Z | | | CW | | 0-0 | 34-22-18 | D00081D | DED | | | D41601J | | CW | | 001-099 |
| 5018B | 24 | G2 | CX | | 4-4 | 34-22-18 | D00081B | B05 | | | D41391J | 5 | | | ALL |
| 5018R | 24 | G2 | CX | | 0-0 | 34-22-18 | D00081B | A05 | | | D41391J | 4 | | | ALL |
| 5018Z | | | CX | | 0-0 | 34-22-18 | D00081B | DED | | | D41391J | | CX | | ALL |
| 5019B | 24 | G2 | CY | | 3-7 | 34-22-18 | D00081A | B05 | | | D41563J | 36 | | | ALL |
| 5019R | 24 | G2 | CY | | 0-0 | 34-22-18 | D00081A | A05 | | | D41563J | 35 | | | ALL |
| 5019Z | | | CY | | 0-0 | 34-22-18 | D00081A | DED | | | D41563J | | CY | | 001-099 |
| 5019Z | | | CY | | 0-0 | 34-22-18 | D00081A | DED | | | D41563J | 37 | | | 115-199 |
| 5020B | 24 | Y2 | RT | | 5-0 | 34-22-18 | D00081D | B03 | | | D43023J | 7 | | | 115-199 |
| 5020R | 24 | Y2 | RT | | 0-0 | 34-22-18 | D00081D | A03 | | | D43023J | 6 | | | 115-199 |
| 5020Z | | | RT | | 0-0 | 34-22-18 | D00081D | DED | | | D43023J | | RT | | 115-199 |
| 5021B | 24 | G2 | GM | | 3-1 | 34-22-35 | D41595J | 17 | | | TB0201Z | 53 | BJ | | 001-099 |
| 5021B | 24 | G2 | GM | | 3-1 | 34-22-35 | TB0201Z | 53 | BJ | | D41595J | 17 | | | 115-199 |
| 5021R | 24 | G2 | GM | | 0-0 | 34-22-35 | D41595J | 16 | | | TB0201Z | 54 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 30

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5021R | 24 | G2 | GM | 0-0 | 34-22-35 | TB0201Z | 54 | BJ | | | D41595J | 16 | | | 115-199 |
| 5021Z | | | GM | 0-0 | 34-22-35 | D41595J | 18 | | | | GD01807 | ST.. | 2 | | 001-099 |
| 5021Z | | | GM | 0-0 | 34-22-35 | GD01807 | ST.. | 2 | | | D41595J | 18 | | | 115-199 |
| 5022B | 24 | G2 | FO | 2-4 | 34-22-39 | D41595J | 2 | | | | TB0201Z | 9 | BJ | | 001-099 |
| 5022B | 24 | G2 | FO | 2-4 | 34-22-39 | TB0201Z | 9 | BJ | | | D41595J | 2 | | | 115-199 |
| 5022R | 24 | G2 | FO | 0-0 | 34-22-39 | D41595J | 1 | | | | TB0201Z | 10 | BJ | | 001-099 |
| 5022R | 24 | G2 | FO | 0-0 | 34-22-39 | TB0201Z | 10 | BJ | | | D41595J | 1 | | | 115-199 |
| 5022Z | | | FO | 0-0 | 34-22-39 | D41595J | 3 | | | | GD01802 | ST.. | 2 | | 001-099 |
| 5022Z | | | FO | 0-0 | 34-22-39 | GD01802 | ST.. | 2 | | | D41595J | 3 | | | 115-199 |
| 5023B | 24 | G2 | FP | 3-7 | 34-22-39 | D41595J | 5 | | | | TB0201Z | 75 | BJ | | 001-099 |
| 5023B | 24 | G2 | FP | 3-7 | 34-22-39 | D41595J | 5 | | | | TB0201Y | C075 | BJ | | 115-199 |
| 5023R | 24 | G2 | FP | 0-0 | 34-22-39 | D41595J | 4 | | | | TB0201Z | 76 | BJ | | 001-099 |
| 5023R | 24 | G2 | FP | 0-0 | 34-22-39 | D41595J | 4 | | | | TB0201Y | C076 | BJ | | 115-199 |
| 5023Z | | | FP | 0-0 | 34-22-39 | D41595J | 6 | | | | GD01810 | ST.. | 2 | | ALL |
| 5024B | 24 | G2 | FQ | 3-6 | 34-22-39 | D41595J | 8 | | | | TB0201Z | 73 | BJ | | 001-099 |
| 5024B | 24 | G2 | FQ | 3-6 | 34-22-39 | D41595J | 8 | | | | TB0201Y | A073 | BJ | | 115-199 |
| 5024R | 24 | G2 | FQ | 0-0 | 34-22-39 | D41595J | 7 | | | | TB0201Z | 74 | BJ | | 001-099 |
| 5024R | 24 | G2 | FQ | 0-0 | 34-22-39 | D41595J | 7 | | | | TB0201Y | A074 | BJ | | 115-199 |
| 5024Z | | | FQ | 0-0 | 34-22-39 | D41595J | 9 | | | | GD01810 | ST.. | 2 | | ALL |
| 5025B | 24 | 7K | DU | 2-2 | 34-43-11 | D41061J | 4 | | | | TB0202Y | A002 | BJ | | 001, 003-099 |
| 5025B | 24 | 7K | DU | 6-0 | 34-43-15 | D41061J | 4 | | | | D21001J | 2 | | | 002 |
| 5025B | 24 | 7K | DU | 2-2 | 34-43-11 | TB0202Y | A002 | BJ | | | D41061J | 4 | | | 115-199 |
| 5025W | 24 | 7K | DU | 0-0 | 34-43-11 | D41061J | 3 | | | | TB0202Y | A001 | BJ | | 001, 003-099 |
| 5025W | 24 | 7K | DU | 0-0 | 34-43-15 | D41061J | 3 | | | | D21001J | 1 | | | 002 |
| 5025W | 24 | 7K | DU | 0-0 | 34-43-11 | TB0202Y | A001 | BJ | | | D41061J | 3 | | | 115-199 |
| 5025Z | | | DU | 0-0 | 34-43-11 | D41061J | 5 | | | | GD01817 | ST.. | 2 | | 001, 003-099 |
| 5025Z | | | DU | 0-0 | 34-43-15 | D41061J | 5 | | | | D21001J | 3 | | | 002 |
| 5025Z | | | DU | 0-0 | 34-43-11 | GD01817 | ST.. | 2 | | | D41061J | 5 | | | 115-199 |
| 5026B | 24 | 7K | DV | 0-6 | 34-43-11 | D00081A | F01 | | | | TB0202Y | A002 | BJ | | 001, 003-099, 115-199 |
| 5026B | 24 | 7K | DV | 5-0 | 34-43-15 | D00081A | F01 | | | | D21001J | 8 | | | 002 |
| 5026W | 24 | 7K | DV | 0-0 | 34-43-11 | D00081A | E01 | | | | TB0202Y | A001 | BJ | | 001, 003-099, 115-199 |
| 5026W | 24 | 7K | DV | 0-0 | 34-43-15 | D00081A | E01 | | | | D21001J | 7 | | | 002 |
| 5026Z | | | DV | 0-0 | 34-43-11 | D00081A | DED | | | | GD01817 | ST.. | 2 | | 001, 003-099 |
| 5026Z | | | DV | 0-0 | 34-43-15 | D00081A | DED | | | | D21001J | 9 | | | 002 |
| 5026Z | | | DV | 0-0 | 34-43-11 | GD01817 | ST.. | 2 | | | D00081A | DED | | | 115-199 |
| 5027B | 24 | 7K | DW | 2-9 | 34-43-11 | D41563J | 45 | | | | TB0202Y | A002 | BJ | | 001, 003-099 |
| 5027B | 24 | 7K | DW | 2-9 | 34-43-11 | TB0202Y | A002 | BJ | | | D41563J | 45 | | | 115-199 |
| 5027W | 24 | 7K | DW | 0-0 | 34-43-11 | D41563J | 46 | | | | TB0202Y | A001 | BJ | | 001, 003-099 |
| 5027W | 24 | 7K | DW | 0-0 | 34-43-11 | TB0202Y | A001 | BJ | | | D41563J | 46 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 31

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|--|---------------|-------------------------|------------------------------------|
| Wire No. | GA CO TY | Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice Effectivity |
| W1171 | 286N1171 | E2-1 INTEGRATION BUNDLE (continued) | | | |
| 5027Z | | DW | 0-0 34-43-11 | D41563J 44 | GD01817 ST.. 2 001, 003-099 |
| 5027Z | | DW | 0-0 34-43-11 | GD01817 ST.. 2 115-199 | |
| 5028B | 24 | G2 HN | 3-2 31-41-12 | D41089J 2 | TB0201Z 47 BJ ALL |
| 5028R | 24 | G2 HN | 0-0 31-41-12 | D41089J 1 | TB0201Z 48 BJ ALL |
| 5028Z | | HN | 0-0 31-41-12 | D41089J 3 | GD01806 ST.. 2 ALL |
| 5029B | 24 | G2 HO | 3-4 31-41-12 | D41089J 5 | TB0201Z 119 BJ ALL |
| 5029R | 24 | G2 HO | 0-0 31-41-12 | D41089J 4 | TB0201Z 120 BJ ALL |
| 5029Z | | HO | 0-0 31-41-12 | D41089J 6 | GD01816 ST.. 2 ALL |
| 5030B | 24 | G2 FH | 3-3 31-31-41 | D41091J 8 | TB0201Y C099 BJ 001-099 |
| 5030B | 24 | G2 FH | 3-3 31-31-21 | D41091J 8 | TB0201Y C099 BJ 115-199 |
| 5030R | 24 | G2 FH | 0-0 31-31-41 | D41091J 7 | TB0201Y C100 BJ 001-099 |
| 5030R | 24 | G2 FH | 0-0 31-31-21 | D41091J 7 | TB0201Y C100 BJ 115-199 |
| 5030Z | | FH | 0-0 31-31-41 | D41091J 9 | GD01813 ST.. 2 001-099 |
| 5030Z | | FH | 0-0 31-31-21 | GD01813 ST.. 2 115-199 | |
| 5031B | 24 | G2 FI | 3-3 31-31-43 | D41091J 11 | TB0201Z 93 BJ 001-099 |
| 5031B | 24 | G2 FI | 3-3 31-31-21 | D41091J 11 | TB0201Z 93 BJ 115-199 |
| 5031R | 24 | G2 FI | 0-0 31-31-43 | D41091J 10 | TB0201Z 94 BJ 001-099 |
| 5031R | 24 | G2 FI | 0-0 31-31-21 | D41091J 10 | TB0201Z 94 BJ 115-199 |
| 5031Z | | FI | 0-0 31-31-43 | D41091J 12 | GD01813 ST.. 2 001-099 |
| 5031Z | | FI | 0-0 31-31-21 | GD01813 ST.. 2 115-199 | |
| 5032B | 24 | G2 FJ | 2-4 31-31-41 | TB0201Y A071 BJ 001-099 | |
| 5032B | 24 | G2 FJ | 2-4 31-31-21 | D41091J 13 | TB0201Y A071 BJ 115-199 |
| 5032R | 24 | G2 FJ | 0-0 31-31-41 | TB0201Y A072 BJ 001-099 | |
| 5032R | 24 | G2 FJ | 0-0 31-31-21 | D41091J 14 | TB0201Y A072 BJ 115-199 |
| 5032Z | | FJ | 0-0 31-31-41 | GD01810 ST.. 2 001-099 | |
| 5032Z | | FJ | 0-0 31-31-21 | D41091J 15 | GD01810 ST.. 2 115-199 |
| 5033B | 24 | G2 FK | 5-0 27-32-11 | D41091J 17 | TB0201Y C066 BJ 001-099 |
| 5033B | 24 | G2 FK | 5-0 27-32-11 | D41091J 17 | TB0201Y A078 BJ 115-199 |
| 5033R | 24 | G2 FK | 0-0 27-32-11 | D41091J 16 | TB0201Y A066 BJ 001-099 |
| 5033R | 24 | G2 FK | 0-0 27-32-11 | D41091J 16 | TB0201Y A077 BJ 115-199 |
| 5033Z | | FK | 0-0 27-32-11 | D41091J 18 | TB0201Y FK 001-099 |
| 5033Z | | FK | 0-0 27-32-11 | TB0201Y FK 115-199 | |
| 5034B | 24 | G2 FG | 3-8 34-12-61 | D42175J 4 | TB0201Z 115 BJ ALL |
| 5034R | 24 | G2 FG | 0-0 34-12-61 | D42175J 3 | TB0201Z 116 BJ ALL |
| 5034Z | | FG | 0-0 34-12-61 | D42175J 5 | GD01815 ST.. 2 001-099 |
| 5034Z | | FG | 0-0 34-12-61 | GD01815 ST.. 2 115-199 | |
| 5035B | 24 | G2 FL | 3-4 34-53-21 | D41089J 46 | TB0201Z 119 BJ ALL |
| 5035R | 24 | G2 FL | 0-0 34-53-21 | D41089J 45 | TB0201Z 120 BJ ALL |
| 5035Z | | FL | 0-0 34-53-21 | D41089J 47 | GD01816 ST.. 2 ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 32

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|-------------------------------------|------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 5036B | 24 | G2 | FM | | 3-4 | 34-53-11 | D41089J | | 43 | | | TB0201Z | 119 | BJ | | ALL |
| 5036R | 24 | G2 | FM | | 0-0 | 34-53-11 | D41089J | | 42 | | | TB0201Z | 120 | BJ | | ALL |
| 5036Z | | | FM | | 0-0 | 34-53-11 | D41089J | | 44 | | | GD01816 | ST.. | 2 | | ALL |
| 5037B | 24 | G2 | EA | | 3-3 | 34-22-81 | D42011J | | 3 | | | TB0201Z | 73 | BJ | | 001-099 |
| 5037R | 24 | G2 | EA | | 0-0 | 34-22-81 | D42011J | | 2 | | | TB0201Z | 74 | BJ | | 001-099 |
| 5037Z | | | EA | | 0-0 | 34-22-81 | D42011J | | 1 | | | GD01810 | ST.. | 2 | *1 | 001-099 |
| 5038B | 24 | G2 | EB | | 3-5 | 34-22-81 | D42011J | | 5 | | | TB0201Z | 75 | BJ | | 001-099 |
| 5038R | 24 | G2 | EB | | 0-0 | 34-22-81 | D42011J | | 4 | | | TB0201Z | 76 | BJ | | 001-099 |
| 5038Z | | | EB | | 0-0 | 34-22-81 | D42011J | | 6 | | | GD01810 | ST.. | 2 | *1 | 001-099 |
| 5040B | 24 | G2 | EM | | 3-3 | 34-12-12 | D00289B | | B02 | | | TB0201Z | 115 | BJ | | ALL |
| 5040R | 24 | G2 | EM | | 0-0 | 34-12-12 | D00289B | | A02 | | | TB0201Z | 116 | BJ | | ALL |
| 5040Z | | | EM | | 0-0 | 34-12-12 | D00289B | | DED | | | GD01815 | ST.. | 2 | | 001-099 |
| 5040Z | | | EM | | 0-0 | 34-12-12 | GD01815 | | ST.. | 2 | | D00289B | DED | | | 115-199 |
| 5041B | 24 | G2 | EP | | 3-4 | 34-12-12 | D00289B | | B08 | | | TB0201Z | 121 | BJ | | ALL |
| 5041R | 24 | G2 | EP | | 0-0 | 34-12-12 | D00289B | | A08 | | | TB0201Z | 122 | BJ | | ALL |
| 5041Z | | | EP | | 0-0 | 34-12-12 | D00289B | | DED | | | GD01816 | ST.. | 2 | | 001-099 |
| 5041Z | | | EP | | 0-0 | 34-12-12 | GD01816 | | ST.. | 2 | | D00289B | DED | | | 115-199 |
| 5042B | 24 | G2 | EO | | 3-8 | 34-12-12 | D41091J | | 52 | | | TB0201Z | 121 | BJ | | ALL |
| 5042R | 24 | G2 | EO | | 0-0 | 34-12-12 | D41091J | | 51 | | | TB0201Z | 122 | BJ | | ALL |
| 5042Z | | | EO | | 0-0 | 34-12-12 | D41091J | | 53 | | | GD01816 | ST.. | 2 | | ALL |
| 5043B | 24 | G2 | PM | | 2-11 | 31-31-43 | D43003J | | 26 | | | TB0201Z | 47 | BJ | | 001-099 |
| 5043B | 24 | G2 | HC | | 2-5 | 31-31-22 | D41905J | | 11 | | | TB0201Z | 47 | BJ | | 115-199 |
| 5043R | 24 | G2 | PM | | 0-0 | 31-31-43 | D43003J | | 25 | | | TB0201Z | 48 | BJ | | 001-099 |
| 5043R | 24 | G2 | HC | | 0-0 | 31-31-22 | D41905J | | 10 | | | TB0201Z | 48 | BJ | | 115-199 |
| 5043Z | | | PM | | 0-0 | 31-31-43 | D43003J | | 27 | | | GD01806 | ST.. | 2 | | 001-099 |
| 5043Z | | | HC | | 0-0 | 31-31-22 | D41905J | | 12 | | | GD01806 | ST.. | 2 | | 115-199 |
| 5044B | 24 | G2 | ET | | 2-5 | 31-51-34 | D41905J | | 49 | | | TB0201Z | 47 | BJ | | 009 |
| 5044B | 24 | G2 | HT | | 2-5 | 31-51-34 | D41905J | | 15 | | | TB0201Z | 47 | BJ | | 115-199 |
| 5044R | 24 | G2 | ET | | 0-0 | 31-51-34 | D41905J | | 48 | | | TB0201Z | 48 | BJ | | 009 |
| 5044R | 24 | G2 | HT | | 0-0 | 31-51-34 | D41905J | | 14 | | | TB0201Z | 48 | BJ | | 115-199 |
| 5044Z | | | ET | | 0-0 | 31-51-34 | D41905J | | 46 | | | GD01806 | ST.. | 2 | | 009 |
| 5044Z | | | HT | | 0-0 | 31-51-34 | D41905J | | 16 | | | GD01806 | ST.. | 2 | | 115-199 |
| 5048B | 24 | G2 | DX | | 2-11 | 34-51-11 | D43003J | | 9 | | | TB0201Y | A037 | BJ | | 001-099 |
| 5048B | 24 | G2 | DX | | 3-10 | 34-51-11 | D41831J | | 3 | | | TB0201Y | A037 | BJ | | 115-199 |
| 5048R | 24 | G2 | DX | | 0-0 | 34-51-11 | D43003J | | 8 | | | TB0201Y | A038 | BJ | | 001-099 |
| 5048R | 24 | G2 | DX | | 0-0 | 34-51-11 | D41831J | | 2 | | | TB0201Y | A038 | BJ | | 115-199 |
| 5048Z | | | DX | | 0-0 | 34-51-11 | D43003J | | 10 | | | GD01805 | ST.. | 2 | | 001-099 |
| 5048Z | | | DX | | 0-0 | 34-51-11 | D41831J | | 4 | | | GD01805 | ST.. | 2 | | 115-199 |
| 5049B | 24 | G2 | HM | | 2-8 | 34-55-11 | D41093J | | 20 | | | TB0201Y | A037 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 33

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|---|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5049R | | 24 | | G2 | HM | 0-0 | 34-55-11 | D41093J | 19 | | | TB0201Y | A038 | BJ | | ALL |
| 5049Z | | | | | HM | 0-0 | 34-55-11 | D41093J | 21 | | | GD01805 | ST.. | 2 | | ALL |
| 5050B | | 24 | | G2 | HK | 2-4 | 34-21-11 | D41595J | 10 | | | TB0201Z | 9 | BJ | | ALL |
| 5050R | | 24 | | G2 | HK | 0-0 | 34-21-11 | D41595J | 11 | | | TB0201Z | 10 | BJ | | ALL |
| 5050Z | | | | | HK | 0-0 | 34-21-11 | D41595J | 12 | | | GD01802 | ST.. | 2 | | ALL |
| 5051B | I | 24 | | G2 | HL | 4-4 | 34-21-11 | D41595J | 13 | | | TB0201Z | 103 | BJ | | 001-099 |
| 5051B | I | 24 | | G2 | HL | 4-4 | 34-21-11 | D41595J | 13 | | | TB0201Z | 112 | BJ | | 115-199 |
| 5051R | I | 24 | | G2 | HL | 0-0 | 34-21-11 | D41595J | 14 | | | TB0201Z | 104 | BJ | | 001-099 |
| 5051R | I | 24 | | G2 | HL | 0-0 | 34-21-11 | D41595J | 14 | | | TB0201Z | 113 | BJ | | 115-199 |
| 5051Z | | | | | HL | 0-0 | 34-21-11 | D41595J | 15 | | | GD01814 | ST.. | 2 | | ALL |
| 5052B | | 24 | | G2 | EJ | 2-7 | 34-13-21 | D42065J | 5 | | | TB0201Z | 121 | BJ | | ALL |
| 5052R | | 24 | | G2 | EJ | 0-0 | 34-13-21 | D42065J | 4 | | | TB0201Z | 122 | BJ | | ALL |
| 5052Z | | | | | EJ | 0-0 | 34-13-21 | D42065J | 6 | | | GD01816 | ST.. | 2 | | ALL |
| 5054B | | 24 | | G2 | EL | 6-4 | 34-13-11 | D00289B | B04 | | | TB0201Z | 9 | BJ | | 001-099 |
| 5054B | | 24 | | G2 | EL | 6-4 | 34-13-11 | TB0201Z | 9 | BJ | | D00289B | B04 | | | 115-199 |
| 5054R | | 24 | | G2 | EL | 0-0 | 34-13-11 | D00289B | A04 | | | TB0201Z | 10 | BJ | | 001-099 |
| 5054R | | 24 | | G2 | EL | 0-0 | 34-13-11 | TB0201Z | 10 | BJ | | D00289B | A04 | | | 115-199 |
| 5054Z | | | | | EL | 0-0 | 34-13-11 | D00289B | DED | | | GD01802 | ST.. | 2 | | 001-099 |
| 5054Z | | | | | EL | 0-0 | 34-13-11 | GD01802 | ST.. | 2 | | D00289B | DED | | | 115-199 |
| 5055B | | 24 | | G2 | DY | 4-5 | 34-51-11 | D42013J | 16 | | | TB0201Z | 101 | BJ | | ALL |
| 5055R | | 24 | | G2 | DY | 0-0 | 34-51-11 | D42013J | 15 | | | TB0201Z | 102 | BJ | | ALL |
| 5055Z | | | | | DY | 0-0 | 34-51-11 | D42013J | 17 | | | GD01814 | ST.. | 2 | | ALL |
| 5056B | | 24 | | G2 | DZ | 4-3 | 34-51-11 | D43003J | 6 | | | TB0201Z | 101 | BJ | | 001-099 |
| 5056B | | 24 | | G2 | DZ | 2-6 | 34-51-11 | TB0201Z | 101 | BJ | | D41831J | 7 | | | 115-199 |
| 5056R | | 24 | | G2 | DZ | 0-0 | 34-51-11 | D43003J | 5 | | | TB0201Z | 102 | BJ | | 001-099 |
| 5056R | | 24 | | G2 | DZ | 0-0 | 34-51-11 | TB0201Z | 102 | BJ | | D41831J | 6 | | | 115-199 |
| 5056Z | | | | | DZ | 0-0 | 34-51-11 | D43003J | 7 | | | GD01814 | ST.. | 2 | | 001-099 |
| 5056Z | | | | | DZ | 0-0 | 34-51-11 | GD01814 | ST.. | 2 | | D41831J | 8 | | | 115-199 |
| 5057B | | 24 | | G2 | HY | 3-3 | 34-55-11 | TB0201Y | A073 | BJ | | D42011J | 48 | | | 115-199 |
| 5057R | | 24 | | G2 | HY | 0-0 | 34-55-11 | TB0201Y | A074 | BJ | | D42011J | 47 | | | 115-199 |
| 5057Z | | | | | HY | 0-0 | 34-55-11 | GD01810 | ST.. | 2 | | D42011J | 49 | | | 115-199 |
| 5058B | | 24 | | G2 | IA | 5-5 | 22-12-11 | D00035A | B10 | | | TB0201Z | 115 | BJ | | ALL |
| 5058R | | 24 | | G2 | IA | 0-0 | 22-12-11 | D00035A | A10 | | | TB0201Z | 116 | BJ | | ALL |
| 5058Z | | | | | IA | 0-0 | 22-12-11 | D00035A | DED | | | GD01815 | ST.. | 2 | | ALL |
| 5059B | | 24 | | G2 | HR | 4-4 | 31-31-42 | D41093J | 47 | | | D00035B | D02 | | | 001-099 |
| 5059B | | 24 | | G2 | FF | 4-4 | 31-31-22 | D41093J | 47 | | | D00035B | D02 | | | 115-199 |
| 5059R | | 24 | | G2 | HR | 0-0 | 31-31-42 | D41093J | 46 | | | D00035B | D01 | | | 001-099 |
| 5059R | | 24 | | G2 | FF | 0-0 | 31-31-22 | D41093J | 46 | | | D00035B | D01 | | | 115-199 |
| 5059Z | | | | | HR | 0-0 | 31-31-42 | D41093J | | | FH | D00035B | DED | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 34

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5059Z | | | | FF | 0-0 | 31-31-22 | D00035B | DED | | | D41093J | | | FF | 115-199 |
| 5060B | 24 | G2 | | HP | 2-6 | 31-25-11 | D42011J | 17 | | | TB0201Y | C099 | BJ | | 001-099 |
| 5060B | 24 | G2 | | HP | 2-6 | 31-25-11 | D42011J | 45 | | | TB0201Y | C099 | BJ | | 115-199 |
| 5060R | 24 | G2 | | HP | 0-0 | 31-25-11 | D42011J | 16 | | | TB0201Y | C100 | BJ | | 001-099 |
| 5060R | 24 | G2 | | HP | 0-0 | 31-25-11 | D42011J | 44 | | | TB0201Y | C100 | BJ | | 115-199 |
| 5060Z | | | | HP | 0-0 | 31-25-11 | D42011J | 18 | | | GD01813 | ST.. | 2 | | 001-099 |
| 5060Z | | | | HP | 0-0 | 31-25-11 | D42011J | 46 | | | GD01813 | ST.. | 2 | | 115-199 |
| 5061B | 24 | G2 | | HQ | 2-10 | 31-25-11 | D00173B | E03 | | | TB0201Y | C099 | BJ | | 001-099 |
| 5061B | 24 | G2 | | HQ | 2-10 | 31-25-11 | TB0201Y | C099 | BJ | | D00173B | E03 | | | 115-199 |
| 5061R | 24 | G2 | | HQ | 0-0 | 31-25-11 | D00173B | D03 | | | TB0201Y | C100 | BJ | | 001-099 |
| 5061R | 24 | G2 | | HQ | 0-0 | 31-25-11 | TB0201Y | C100 | BJ | | D00173B | D03 | | | 115-199 |
| 5061Z | | | | HQ | 0-0 | 31-25-11 | D00173B | DED | | | GD01813 | ST.. | 2 | | ALL |
| 5062B | 24 | G2 | | GI | 2-8 | 34-46-12 | D41429J | 5 | | | TB0201Z | 55 | BJ | | ALL |
| 5062R | 24 | G2 | | GI | 0-0 | 34-46-12 | D41429J | 4 | | | TB0201Z | 56 | BJ | | ALL |
| 5062Z | | | | GI | 0-0 | 34-46-12 | D41429J | 6 | | | GD01808 | ST.. | 2 | | ALL |
| 5063B | 24 | G2 | | AA | 2-8 | 34-46-12 | D41429J | 10 | | | TB0201Z | 47 | BJ | | 001, 003-099 |
| 5063B | 22 | GU | | AA | 5-0 | 34-46-12 | D41429J | 10 | | | SM00098 | | 9 | | 002 |
| 5063B | 24 | G2 | | AA | 2-8 | 34-46-12 | TB0201Z | 47 | BJ | | D41429J | 10 | | | 115-199 |
| 5063R | 24 | G2 | | AA | 0-0 | 34-46-12 | D41429J | 9 | | | TB0201Z | 48 | BJ | | 001, 003-099 |
| 5063R | 22 | GU | | AA | 0-0 | 34-46-12 | D41429J | 9 | | | SM00099 | | 9 | | 002 |
| 5063R | 24 | G2 | | AA | 0-0 | 34-46-12 | TB0201Z | 48 | BJ | | D41429J | 9 | | | 115-199 |
| 5063Z | | | | AA | 0-0 | 34-46-12 | D41429J | 8 | | | GD01807 | ST.. | 2 | | 001-099 |
| 5063Z | | | | AA | 0-0 | 34-46-12 | GD01807 | ST.. | 2 | | D41429J | 8 | | | 115-199 |
| 5064B | 24 | G2 | | AB | 4-0 | 34-46-12 | D41429J | 13 | | | TB0201Z | 93 | BJ | | 001-099 |
| 5064B | 24 | G2 | | AB | 4-0 | 34-46-12 | TB0201Z | 93 | BJ | | D41429J | 13 | | | 115-199 |
| 5064R | 24 | G2 | | AB | 0-0 | 34-46-12 | D41429J | 12 | | | TB0201Z | 94 | BJ | | 001-099 |
| 5064R | 24 | G2 | | AB | 0-0 | 34-46-12 | TB0201Z | 94 | BJ | | D41429J | 12 | | | 115-199 |
| 5064Z | | | | AB | 0-0 | 34-46-12 | D41429J | 11 | | | GD01813 | ST.. | 2 | | 001-099 |
| 5064Z | | | | AB | 0-0 | 34-46-12 | GD01813 | ST.. | 2 | | D41429J | 11 | | | 115-199 |
| 5065B | 24 | G2 | | AC | 4-6 | 34-46-12 | D41429J | 16 | | | TB0201Z | 121 | BJ | | 001-099 |
| 5065B | 24 | G2 | | AC | 4-6 | 34-46-12 | TB0201Z | 121 | BJ | | D41429J | 16 | | | 115-199 |
| 5065R | 24 | G2 | | AC | 0-0 | 34-46-12 | D41429J | 15 | | | TB0201Z | 122 | BJ | | 001-099 |
| 5065R | 24 | G2 | | AC | 0-0 | 34-46-12 | TB0201Z | 122 | BJ | | D41429J | 15 | | | 115-199 |
| 5065Z | | | | AC | 0-0 | 34-46-12 | D41429J | 14 | | | GD01816 | ST.. | 2 | | 001-099 |
| 5065Z | | | | AC | 0-0 | 34-46-12 | GD01816 | ST.. | 2 | | D41429J | 14 | | | 115-199 |
| 5066B | 24 | G2 | | AI | 3-7 | 34-61-11 | D00173A | E13 | | | D41081J | 7 | | | 001-099 |
| 5066B | 24 | G2 | | AI | 3-7 | 34-61-11 | D41081J | 7 | | | D00173A | E13 | | | 115-199 |
| 5066R | 24 | G2 | | AI | 0-0 | 34-61-11 | D00173A | D13 | | | D41081J | 8 | | | 001-099 |
| 5066R | 24 | G2 | | AI | 0-0 | 34-61-11 | D41081J | 8 | | | D00173A | D13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 35

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5066Z | | | | AI | 0-0 | 34-61-11 | D00173A | DED | | | D41081J | | | AI | 001-099 |
| 5066Z | | | | AI | 0-0 | 34-61-11 | D41081J | | | AI | D00173A | DED | | | 115-199 |
| 5067B | 24 | G2 | | AD | 2-4 | 34-61-11 | D41081J | 4 | | | TB0201Y | C077 | BJ | | ALL |
| 5067R | 24 | G2 | | AD | 0-0 | 34-61-11 | D41081J | 5 | | | TB0201Y | C078 | BJ | | ALL |
| 5067Z | | | | AD | 0-0 | 34-61-11 | D41081J | 6 | | | GD01811 | ST.. | 2 | | ALL |
| 5068B | 24 | G2 | | AE | 3-3 | 34-61-11 | D00173A | B09 | | | TB0201Y | C077 | BJ | | ALL |
| 5068R | 24 | G2 | | AE | 0-0 | 34-61-11 | D00173A | A09 | | | TB0201Y | C078 | BJ | | ALL |
| 5068Z | | | | AE | 0-0 | 34-61-11 | D00173A | DED | | | GD01811 | ST.. | 2 | | ALL |
| 5069B | 24 | G2 | | AF | 2-10 | 34-61-11 | D41817J | 17 | | | TB0201Y | C077 | BJ | | ALL |
| 5069R | 24 | G2 | | AF | 0-0 | 34-61-11 | D41817J | 18 | | | TB0201Y | C078 | BJ | | ALL |
| 5069Z | | | | AF | 0-0 | 34-61-11 | D41817J | 16 | | | GD01811 | ST.. | 2 | | ALL |
| 5070B | 24 | G2 | | AG | 3-2 | 34-61-11 | D41817J | 14 | | | D41081J | 1 | | | 001-099 |
| 5070B | 24 | G2 | | AG | 3-2 | 34-61-11 | D41081J | 1 | | | D41817J | 14 | | | 115-199 |
| 5070R | 24 | G2 | | AG | 0-0 | 34-61-11 | D41817J | 15 | | | D41081J | 2 | | | 001-099 |
| 5070R | 24 | G2 | | AG | 0-0 | 34-61-11 | D41081J | 2 | | | D41817J | 15 | | | 115-199 |
| 5070Z | | | | AG | 0-0 | 34-61-11 | D41817J | 13 | | | D41081J | 3 | | | 001-099 |
| 5070Z | | | | AG | 0-0 | 34-61-11 | D41081J | 3 | | | D41817J | 13 | | | 115-199 |
| 5071B | 24 | G2 | | AH | 3-1 | 34-61-11 | D00173A | B13 | | | D41817J | 22 | | | 001-099 |
| 5071B | 24 | G2 | | AH | 3-1 | 34-61-11 | D41817J | 22 | | | D00173A | B13 | | | 115-199 |
| 5071R | 24 | G2 | | AH | 0-0 | 34-61-11 | D00173A | A13 | | | D41817J | 21 | | | 001-099 |
| 5071R | 24 | G2 | | AH | 0-0 | 34-61-11 | D41817J | 21 | | | D00173A | A13 | | | 115-199 |
| 5071Z | | | | AH | 0-0 | 34-61-11 | D00173A | DED | | | D41817J | | | AH | 001-099 |
| 5071Z | | | | AH | 0-0 | 34-61-11 | D41817J | | | AH | D00173A | DED | | | 115-199 |
| 5072B | 24 | G2 | | AU | 3-4 | 34-61-13 | D00173B | E01 | | | D41601J | 6 | | | 001-099 |
| 5072B | 24 | G2 | | AU | 3-4 | 34-61-13 | D41601J | 6 | | | D00173B | E01 | | | 115-199 |
| 5072R | 24 | G2 | | AU | 0-0 | 34-61-13 | D00173B | D01 | | | D41601J | 5 | | | 001-099 |
| 5072R | 24 | G2 | | AU | 0-0 | 34-61-13 | D41601J | 5 | | | D00173B | D01 | | | 115-199 |
| 5072Z | | | | AU | 0-0 | 34-61-13 | D00173B | DED | | | D41601J | | | AU | 001-099 |
| 5072Z | | | | AU | 0-0 | 34-61-13 | D41601J | | | AU | D00173B | DED | | | 115-199 |
| 5073B | 24 | G2 | | AV | 3-4 | 34-61-13 | D00173B | H07 | | | D41601J | 9 | | | 001-099 |
| 5073B | 24 | G2 | | AV | 3-4 | 34-61-13 | D41601J | 9 | | | D00173B | H07 | | | 115-199 |
| 5073R | 24 | G2 | | AV | 0-0 | 34-61-13 | D00173B | G07 | | | D41601J | 8 | | | 001-099 |
| 5073R | 24 | G2 | | AV | 0-0 | 34-61-13 | D41601J | 8 | | | D00173B | G07 | | | 115-199 |
| 5073Z | | | | AV | 0-0 | 34-61-13 | D00173B | DED | | | D41601J | | | AV | 001-099 |
| 5073Z | | | | AV | 0-0 | 34-61-13 | D41601J | | | AV | D00173B | DED | | | 115-199 |
| 5074B | 24 | G2 | | AW | 3-4 | 34-61-13 | D00173B | E05 | | | D41601J | 13 | | | 001-099 |
| 5074B | 24 | G2 | | AW | 3-4 | 34-61-13 | D41601J | 13 | | | D00173B | E05 | | | 115-199 |
| 5074R | 24 | G2 | | AW | 0-0 | 34-61-13 | D00173B | D05 | | | D41601J | 12 | | | 001-099 |
| 5074R | 24 | G2 | | AW | 0-0 | 34-61-13 | D41601J | 12 | | | D00173B | D05 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 36

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5074Z | | | | AW | 0-0 | 34-61-13 | D00173B | DED | | | D41601J | | | AW | 001-099 |
| 5074Z | | | | AW | 0-0 | 34-61-13 | D41601J | | | AW | D00173B | DED | | | 115-199 |
| 5075B | 24 | G2 | | AX | 3-4 | 34-61-13 | D00173B | B03 | | | D41601J | 16 | | | 001-099 |
| 5075B | 24 | G2 | | AX | 3-4 | 34-61-13 | D41601J | 16 | | | D00173B | B03 | | | 115-199 |
| 5075R | 24 | G2 | | AX | 0-0 | 34-61-13 | D00173B | A03 | | | D41601J | 15 | | | 001-099 |
| 5075R | 24 | G2 | | AX | 0-0 | 34-61-13 | D41601J | 15 | | | D00173B | A03 | | | 115-199 |
| 5075Z | | | | AX | 0-0 | 34-61-13 | D00173B | DED | | | D41601J | | | AX | 001-099 |
| 5075Z | | | | AX | 0-0 | 34-61-13 | D41601J | | | AX | D00173B | DED | | | 115-199 |
| 5076B | 24 | G2 | | AY | 4-6 | 34-61-14 | D00173A | H03 | | | TB0201Y | C030 | BJ | | ALL |
| 5076R | 24 | G2 | | AY | 0-0 | 34-61-14 | D00173A | G03 | | | TB0201Y | A030 | BJ | | ALL |
| 5076Z | | | | AY | 0-0 | 34-61-14 | D00173A | DED | | | GD01805 | ST.. | 2 | | ALL |
| 5077B | 24 | G2 | | AZ | 3-9 | 34-61-14 | D00173A | E05 | | | D41089J | 14 | | | 001-099 |
| 5077B | 24 | G2 | | AZ | 3-9 | 34-61-14 | D41089J | 14 | | | D00173A | E05 | | | 115-199 |
| 5077R | 24 | G2 | | AZ | 0-0 | 34-61-14 | D00173A | D05 | | | D41089J | 13 | | | 001-099 |
| 5077R | 24 | G2 | | AZ | 0-0 | 34-61-14 | D41089J | 13 | | | D00173A | D05 | | | 115-199 |
| 5077Z | | | | AZ | 0-0 | 34-61-14 | D00173A | DED | | | D41089J | | | AZ | 001-099 |
| 5077Z | | | | AZ | 0-0 | 34-61-14 | D41089J | | | AZ | D00173A | DED | | | 115-199 |
| 5078B | 24 | G2 | | BB | 4-6 | 34-61-14 | D00173A | H07 | | | TB0201Y | A025 | BJ | | ALL |
| 5078R | 24 | G2 | | BB | 0-0 | 34-61-14 | D00173A | G07 | | | TB0201Y | A026 | BJ | | ALL |
| 5078Z | | | | BB | 0-0 | 34-61-14 | D00173A | DED | | | GD01804 | ST.. | 2 | | ALL |
| 5079B | 24 | G2 | | BC | 4-2 | 34-61-14 | D00173A | B05 | | | TB0201Z | 53 | BJ | | 001-099 |
| 5079B | 24 | G2 | | BC | 4-2 | 34-61-14 | TB0201Z | 53 | BJ | | D00173A | B05 | | | 115-199 |
| 5079R | 24 | G2 | | BC | 0-0 | 34-61-14 | D00173A | A05 | | | TB0201Z | 54 | BJ | | 001-099 |
| 5079R | 24 | G2 | | BC | 0-0 | 34-61-14 | TB0201Z | 54 | BJ | | D00173A | A05 | | | 115-199 |
| 5079Z | | | | BC | 0-0 | 34-61-14 | D00173A | DED | | | GD01807 | ST.. | 2 | | 001-099 |
| 5079Z | | | | BC | 0-0 | 34-61-14 | GD01807 | ST.. | 2 | | D00173A | DED | | | 115-199 |
| 5080B | 24 | G2 | | BA | 3-2 | 34-61-14 | D00173A | D09 | | | D42183J | 1 | | | 001-099 |
| 5080B | 24 | G2 | | BA | 3-2 | 34-61-14 | D42183J | 1 | | | D00173A | D09 | | | 115-199 |
| 5080R | 24 | G2 | | BA | 0-0 | 34-61-14 | D00173A | E09 | | | D42183J | 2 | | | 001-099 |
| 5080R | 24 | G2 | | BA | 0-0 | 34-61-14 | D42183J | 2 | | | D00173A | E09 | | | 115-199 |
| 5080Z | | | | BA | 0-0 | 34-61-14 | D00173A | DED | | | D42183J | | | BA | 001-099 |
| 5080Z | | | | BA | 0-0 | 34-61-14 | D42183J | | | BA | D00173A | DED | | | 115-199 |
| 5081B | 24 | G2 | | BD | 3-2 | 34-61-15 | D00173A | H11 | | | D42183J | 4 | | | 001-099 |
| 5081B | 24 | G2 | | BD | 3-2 | 34-61-15 | D42183J | 4 | | | D00173A | H11 | | | 115-199 |
| 5081R | 24 | G2 | | BD | 0-0 | 34-61-15 | D00173A | G11 | | | D42183J | 3 | | | 001-099 |
| 5081R | 24 | G2 | | BD | 0-0 | 34-61-15 | D42183J | 3 | | | D00173A | G11 | | | 115-199 |
| 5081Z | | | | BD | 0-0 | 34-61-15 | D00173A | DED | | | D42183J | | | BD | 001-099 |
| 5081Z | | | | BD | 0-0 | 34-61-15 | D42183J | | | BD | D00173A | DED | | | 115-199 |
| 5082B | 24 | G2 | | BE | 2-10 | 34-61-15 | D00173A | H09 | | | TB0201Z | 103 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 37

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | |
| 5082B | 24 | G2 | BE | 2-10 | 34-61-15 | D00173A | H09 | | | TB0201Z | 112 | BJ | | 115-199 |
| 5082R | 24 | G2 | BE | 0-0 | 34-61-15 | D00173A | G09 | | | TB0201Z | 104 | BJ | | 001-099 |
| 5082R | 24 | G2 | BE | 0-0 | 34-61-15 | D00173A | G09 | | | TB0201Z | 113 | BJ | | 115-199 |
| 5082Z | | | BE | 0-0 | 34-61-15 | D00173A | DED | | | GD01814 | ST.. | 2 | | 001-099 |
| 5082Z | | | BE | 0-0 | 34-61-15 | GD01814 | ST.. | 2 | | D00173A | DED | | | 115-199 |
| 5083B | 24 | G2 | BG | 3-3 | 34-61-15 | D00173B | E07 | | | TB0201Z | 79 | BJ | | ALL |
| 5083R | 24 | G2 | BG | 0-0 | 34-61-15 | D00173B | D07 | | | TB0201Z | 80 | BJ | | ALL |
| 5083Z | | | BG | 0-0 | 34-61-15 | D00173B | DED | | | GD01811 | ST.. | 2 | | ALL |
| 5084B | 24 | G2 | BF | 2-5 | 34-61-15 | D41563J | 8 | | | TB0201Z | 79 | BJ | | ALL |
| 5084R | 24 | G2 | BF | 0-0 | 34-61-15 | D41563J | 7 | | | TB0201Z | 80 | BJ | | ALL |
| 5084Z | | | BF | 0-0 | 34-61-15 | D41563J | 9 | | | GD01811 | ST.. | 2 | | ALL |
| 5085B | 24 | G2 | BH | 2-5 | 34-61-15 | D41089J | 20 | | | TB0201Z | 79 | BJ | | ALL |
| 5085R | 24 | G2 | BH | 0-0 | 34-61-15 | D41089J | 19 | | | TB0201Z | 80 | BJ | | ALL |
| 5085Z | | | BH | 0-0 | 34-61-15 | D41089J | 18 | | | GD01811 | ST.. | 2 | | ALL |
| 5086B | 24 | G2 | BI | 3-4 | 34-61-21 | D00173A | H13 | | | D41601J | 18 | | | ALL |
| 5086R | 24 | G2 | BI | 0-0 | 34-61-21 | D00173A | G13 | | | D41601J | 19 | | | ALL |
| 5086Z | | | BI | 0-0 | 34-61-21 | D00173A | DED | | | D41601J | | | BI | ALL |
| 5087B | 24 | G2 | BJ | 3-4 | 34-61-21 | D00173A | E11 | | | D41601J | 23 | | | ALL |
| 5087R | 24 | G2 | BJ | 0-0 | 34-61-21 | D00173A | D11 | | | D41601J | 24 | | | ALL |
| 5087Z | | | BJ | 0-0 | 34-61-21 | D00173A | DED | | | D41601J | | | BJ | ALL |
| 5088B | 24 | G2 | BK | 3-4 | 34-61-21 | D00173B | H01 | | | D41601J | 26 | | | ALL |
| 5088R | 24 | G2 | BK | 0-0 | 34-61-21 | D00173B | G01 | | | D41601J | 25 | | | ALL |
| 5088Z | | | BK | 0-0 | 34-61-21 | D00173B | DED | | | D41601J | | | BK | ALL |
| 5089B | 24 | G2 | BL | 2-6 | 34-61-22 | D41601J | 29 | | | TB0201Y | C097 | BJ | | ALL |
| 5089R | 24 | G2 | BL | 0-0 | 34-61-22 | D41601J | 28 | | | TB0201Y | C098 | BJ | | ALL |
| 5089Z | | | BL | 0-0 | 34-61-22 | D41601J | 30 | | | GD01813 | ST.. | 2 | | ALL |
| 5090B | 24 | G2 | EW | 4-4 | 22-41-12 | D00035A | A02 | | | D41093J | 2 | | | ALL |
| 5090R | 24 | G2 | EW | 0-0 | 22-41-12 | D00035A | A01 | | | D41093J | 1 | | | ALL |
| 5090Z | | | EW | 0-0 | 22-41-12 | D00035A | DED | | | D41093J | | | EW | ALL |
| 5091B | 24 | G2 | EX | 4-3 | 22-41-11 | D00035B | C04 | | | D41091J | 41 | | | ALL |
| 5091R | 24 | G2 | EX | 0-0 | 22-41-11 | D00035B | C03 | | | D41091J | 40 | | | ALL |
| 5091Z | | | EX | 0-0 | 22-41-11 | D00035B | DED | | | D41091J | | | EX | ALL |
| 5092B | 24 | G2 | EY | 2-9 | 22-41-11 | D41091J | 47 | | | TB0201Z | 79 | BJ | | ALL |
| 5092R | 24 | G2 | EY | 0-0 | 22-41-11 | D41091J | 46 | | | TB0201Z | 80 | BJ | | ALL |
| 5092Z | | | EY | 0-0 | 22-41-11 | D41091J | 45 | | | GD01811 | ST.. | 2 | | ALL |
| 5093B | 24 | G2 | IF | 2-8 | 31-51-21 | D41093J | 44 | | | TB0201Z | 47 | BJ | | ALL |
| 5093R | 24 | G2 | IF | 0-0 | 31-51-21 | D41093J | 45 | | | TB0201Z | 48 | BJ | | ALL |
| 5093Z | | | IF | 0-0 | 31-51-21 | D41093J | 51 | | | GD01807 | ST.. | 2 | | ALL |
| 5094B | 24 | G2 | FA | 2-3 | 22-32-11 | D41817J | 3 | | | TB0201Z | 115 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 38

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5094R | 24 | | G2 | FA | 0-0 | 22-32-11 | D41817J | | 2 | | TB0201Z | 116 | BJ | | ALL |
| 5094Z | | | | FA | 0-0 | 22-32-11 | D41817J | | 4 | | GD01815 | ST.. | 2 | | ALL |
| 5095B | 24 | | G2 | FB | 2-4 | 22-32-11 | D41817J | | 6 | | TB0201Z | 103 | BJ | | ALL |
| 5095R | 24 | | G2 | FB | 0-0 | 22-32-11 | D41817J | | 5 | | TB0201Z | 104 | BJ | | ALL |
| 5095Z | | | | FB | 0-0 | 22-32-11 | D41817J | | 7 | | GD01814 | ST.. | 2 | | ALL |
| 5096B | 24 | | G2 | FC | 3-8 | 22-24-11 | D41091J | | 38 | | TB0201Z | 115 | BJ | | ALL |
| 5096R | 24 | | G2 | FC | 0-0 | 22-24-11 | D41091J | | 37 | | TB0201Z | 116 | BJ | | ALL |
| 5096Z | | | | FC | 0-0 | 22-24-11 | D41091J | | 39 | | GD01815 | ST.. | 2 | | ALL |
| 5098B | 24 | | G2 | FE | 3-6 | 22-22-11 | D41091J | | 33 | | TB0201Y | A011 | BJ | | ALL |
| 5098R | 24 | | G2 | FE | 0-0 | 22-22-11 | D41091J | | 32 | | TB0201Y | A012 | BJ | | ALL |
| 5098Z | | | | FE | 0-0 | 22-22-11 | D41091J | | 34 | | GD01802 | ST.. | 2 | | ALL |
| 5099B | 24 | | G2 | BW | 2-5 | 22-12-11 | D42013J | | 6 | | TB0201Y | A011 | BJ | | ALL |
| 5099R | 24 | | G2 | BW | 0-0 | 22-12-11 | D42013J | | 5 | | TB0201Y | A012 | BJ | | ALL |
| 5099Z | | | | BW | 0-0 | 22-12-11 | D42013J | | 7 | | GD01802 | ST.. | 2 | | ALL |
| 5100B | 24 | | G2 | BX | 3-0 | 22-12-11 | D00035B | | B04 | | TB0201Y | A011 | BJ | | ALL |
| 5100R | 24 | | G2 | BX | 0-0 | 22-12-11 | D00035B | | B03 | | TB0201Y | A012 | BJ | | ALL |
| 5100Z | | | | BX | 0-0 | 22-12-11 | D00035B | | DED | | GD01802 | ST.. | 2 | | ALL |
| 5101B | 24 | | G2 | BY | 5-0 | 22-12-11 | D00035A | | D09 | | TB0201Z | 103 | BJ | | ALL |
| 5101R | 24 | | G2 | BY | 0-0 | 22-12-11 | D00035A | | C09 | | TB0201Z | 104 | BJ | | ALL |
| 5101Z | | | | BY | 0-0 | 22-12-11 | D00035A | | DED | | GD01814 | ST.. | 2 | | 001-099 |
| 5101Z | | | | BY | 0-0 | 22-12-11 | GD01814 | | ST.. | 2 | D00035A | DED | | | 115-199 |
| 5102B | 24 | | G2 | CC | 4-3 | 22-12-11 | D00035B | | C02 | | D41091J | 20 | | | ALL |
| 5102R | 24 | | G2 | CC | 0-0 | 22-12-11 | D00035B | | C01 | | D41091J | 19 | | | ALL |
| 5102Z | | | | CC | 0-0 | 22-12-11 | D00035B | | DED | | D41091J | | | CC | 001-099 |
| 5102Z | | | | CC | 0-0 | 22-12-11 | D41091J | | | CC | D00035B | DED | | | 115-199 |
| 5103B | 24 | | G2 | CE | 3-3 | 22-12-11 | D00035B | | B02 | | TB0201Y | C027 | BJ | | ALL |
| 5103R | 24 | | G2 | CE | 0-0 | 22-12-11 | D00035B | | B01 | | TB0201Y | C028 | BJ | | ALL |
| 5103Z | | | | CE | 0-0 | 22-12-11 | D00035B | | DED | | GD01804 | ST.. | 2 | | 001-099 |
| 5103Z | | | | CE | 0-0 | 22-12-11 | GD01804 | | ST.. | 2 | D00035B | DED | | | 115-199 |
| 5104B | 24 | | G2 | CF | 2-8 | 22-12-11 | D41595J | | 30 | | TB0201Y | C027 | BJ | | ALL |
| 5104R | 24 | | G2 | CF | 0-0 | 22-12-11 | D41595J | | 29 | | TB0201Y | C028 | BJ | | ALL |
| 5104Z | | | | CF | 0-0 | 22-12-11 | D41595J | | 31 | | GD01804 | ST.. | 2 | | 001-099 |
| 5104Z | | | | CF | 0-0 | 22-12-11 | GD01804 | | ST.. | 2 | D41595J | 31 | | | 115-199 |
| 5105B | 24 | | G2 | CG | 3-8 | 22-12-11 | D00081A | | B01 | | TB0201Y | C027 | BJ | | ALL |
| 5105R | 24 | | G2 | CG | 0-0 | 22-12-11 | D00081A | | A01 | | TB0201Y | C028 | BJ | | ALL |
| 5105Z | | | | CG | 0-0 | 22-12-11 | D00081A | | DED | | GD01804 | ST.. | 2 | | 001-099 |
| 5105Z | | | | CG | 0-0 | 22-12-11 | GD01804 | | ST.. | 2 | D00081A | DED | | | 115-199 |
| 5106B | 24 | | G2 | CH | 3-1 | 22-12-21 | D00081D | | B01 | | D41745J | 5 | | | 001-099 |
| 5106B | 24 | | G2 | CH | 3-1 | 22-12-21 | D41745J | | 5 | | D00081D | B01 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 39

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5106R | 24 | G2 | CH | | 0-0 | 22-12-21 | D00081D | A01 | | | D41745J | 6 | | | 001-099 |
| 5106R | 24 | G2 | CH | | 0-0 | 22-12-21 | D41745J | 6 | | | D00081D | A01 | | | 115-199 |
| 5106Z | | | CH | | 0-0 | 22-12-21 | D00081D | DED | | | D41745J | | CH | | 001-099 |
| 5106Z | | | CH | | 0-0 | 22-12-21 | D41745J | | CH | | D00081D | DED | | | 115-199 |
| 5108B | 24 | G2 | FR | | 4-4 | 22-12-31 | D00081B | B01 | | | D41391J | 11 | | | ALL |
| 5108R | 24 | G2 | FR | | 0-0 | 22-12-31 | D00081B | A01 | | | D41391J | 10 | | | ALL |
| 5108Z | | | FR | | 0-0 | 22-12-31 | D00081B | DED | | | D41391J | | FR | | 001-099 |
| 5108Z | | | FR | | 0-0 | 22-12-31 | D41391J | | FR | | D00081B | DED | | | 115-199 |
| 5109B | 24 | G2 | FS | | 2-8 | 22-13-11 | D42013J | 9 | | | TB0201Y | A025 | BJ | | ALL |
| 5109R | 24 | G2 | FS | | 0-0 | 22-13-11 | D42013J | 8 | | | TB0201Y | A026 | BJ | | ALL |
| 5109Z | | | FS | | 0-0 | 22-13-11 | D42013J | 10 | | | GD01804 | ST.. | 2 | | ALL |
| 5110B | 24 | G2 | FT | | 2-8 | 22-13-11 | D41595J | 33 | | | TB0201Y | A025 | BJ | | ALL |
| 5110R | 24 | G2 | FT | | 0-0 | 22-13-11 | D41595J | 32 | | | TB0201Y | A026 | BJ | | ALL |
| 5110Z | | | FT | | 0-0 | 22-13-11 | D41595J | 34 | | | GD01804 | ST.. | 2 | | ALL |
| 5111B | 24 | G2 | FU | | 3-3 | 22-13-11 | D00035A | B09 | | | TB0201Y | A025 | BJ | | ALL |
| 5111R | 24 | G2 | FU | | 0-0 | 22-13-11 | D00035A | A09 | | | TB0201Y | A026 | BJ | | ALL |
| 5111Z | | | FU | | 0-0 | 22-13-11 | D00035A | DED | | | GD01804 | ST.. | 2 | | ALL |
| 5112B | 24 | G2 | FX | | 2-11 | 22-13-11 | D00035B | E02 | | | D41595J | 36 | | | ALL |
| 5112R | 24 | G2 | FX | | 0-0 | 22-13-11 | D00035B | E01 | | | D41595J | 35 | | | ALL |
| 5112Z | | | FX | | 0-0 | 22-13-11 | D00035B | DED | | | D41595J | | FX | | 001-099 |
| 5112Z | | | FX | | 0-0 | 22-13-11 | D41595J | | FX | | D00035B | DED | | | 115-199 |
| 5113B | 24 | G2 | NA | | 4-1 | 22-13-11 | D41905J | 2 | | | D00035B | A02 | | | 001-099 |
| 5113B | 24 | G2 | NA | | 4-0 | 22-13-11 | D43003J | 44 | | | D00035B | A02 | | | 115-199 |
| 5113R | 24 | G2 | NA | | 0-0 | 22-13-11 | D41905J | 1 | | | D00035B | A01 | | | 001-099 |
| 5113R | 24 | G2 | NA | | 0-0 | 22-13-11 | D43003J | 43 | | | D00035B | A01 | | | 115-199 |
| 5113Z | | | NA | | 0-0 | 22-13-11 | D41905J | | NA | | D00035B | DED | | | 001-099 |
| 5113Z | | | NA | | 0-0 | 22-13-11 | D43003J | | NA | | D00035B | DED | | | 115-199 |
| 5115B | 24 | G2 | BM | | 2-3 | 34-61-23 | D41563J | 24 | | | TB0201Z | 101 | BJ | | 001-099 |
| 5115B | 24 | G2 | BM | | 2-3 | 34-61-23 | TB0201Z | 101 | BJ | | D41563J | 24 | | | 115-199 |
| 5115R | 24 | G2 | BM | | 0-0 | 34-61-23 | D41563J | 23 | | | TB0201Z | 102 | BJ | | 001-099 |
| 5115R | 24 | G2 | BM | | 0-0 | 34-61-23 | TB0201Z | 102 | BJ | | D41563J | 23 | | | 115-199 |
| 5115Z | | | BM | | 0-0 | 34-61-23 | D41563J | 25 | | | GD01814 | ST.. | 2 | | 001-099 |
| 5115Z | | | BM | | 0-0 | 34-61-23 | GD01814 | ST.. | 2 | | D41563J | 25 | | | 115-199 |
| 5116B | 24 | G2 | BN | | 2-4 | 34-61-23 | D41563J | 13 | | | TB0201Z | 95 | BJ | | 001-099 |
| 5116B | 24 | G2 | BN | | 2-4 | 34-61-23 | TB0201Z | 95 | BJ | | D41563J | 13 | | | 115-199 |
| 5116R | 24 | G2 | BN | | 0-0 | 34-61-23 | D41563J | 12 | | | TB0201Z | 96 | BJ | | 001-099 |
| 5116R | 24 | G2 | BN | | 0-0 | 34-61-23 | TB0201Z | 96 | BJ | | D41563J | 12 | | | 115-199 |
| 5116Z | | | BN | | 0-0 | 34-61-23 | D41563J | 14 | | | GD01813 | ST.. | 2 | | 001-099 |
| 5116Z | | | BN | | 0-0 | 34-61-23 | GD01813 | ST.. | 2 | | D41563J | 14 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 40

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|-------------------------------------|---------|----------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5117B | 24 | G2 | BO | | 2-8 | 34-61-23 | D41563J | 16 | | | TB0201Z | 117 | BJ | | 001-099 |
| 5117B | 24 | G2 | BO | | 2-8 | 34-61-23 | TB0201Z | 117 | BJ | | D41563J | 16 | | | 115-199 |
| 5117R | 24 | G2 | BO | | 0-0 | 34-61-23 | D41563J | 15 | | | TB0201Z | 118 | BJ | | 001-099 |
| 5117R | 24 | G2 | BO | | 0-0 | 34-61-23 | TB0201Z | 118 | BJ | | D41563J | 15 | | | 115-199 |
| 5117Z | | | BO | | 0-0 | 34-61-23 | D41563J | 17 | | | GD01816 | ST.. | 2 | | ALL |
| 5118B | 24 | G2 | BP | | 2-4 | 34-61-23 | D41563J | 19 | | | TB0201Z | 93 | BJ | | 001-099 |
| 5118B | 24 | G2 | BP | | 2-4 | 34-61-23 | TB0201Z | 93 | BJ | | D41563J | 19 | | | 115-199 |
| 5118R | 24 | G2 | BP | | 0-0 | 34-61-23 | D41563J | 18 | | | TB0201Z | 94 | BJ | | 001-099 |
| 5118R | 24 | G2 | BP | | 0-0 | 34-61-23 | TB0201Z | 94 | BJ | | D41563J | 18 | | | 115-199 |
| 5118Z | | | BP | | 0-0 | 34-61-23 | D41563J | 20 | | | GD01813 | ST.. | 2 | | 001-099 |
| 5118Z | | | BP | | 0-0 | 34-61-23 | GD01813 | ST.. | 2 | | D41563J | 20 | | | 115-199 |
| 5119B | 24 | G2 | AJ | | 4-2 | 34-61-12 | D00173A | H01 | | | TB0201Z | 55 | BJ | | ALL |
| 5119R | 24 | G2 | AJ | | 0-0 | 34-61-12 | D00173A | G01 | | | TB0201Z | 56 | BJ | | ALL |
| 5119Z | | | AJ | | 0-0 | 34-61-12 | D00173A | DED | | | GD01808 | ST.. | 2 | | ALL |
| 5120B | 24 | G2 | AK | | 3-1 | 34-61-12 | D00173A | H05 | | | D41563J | 2 | | | ALL |
| 5120R | 24 | G2 | AK | | 0-0 | 34-61-12 | D00173A | G05 | | | D41563J | 1 | | | ALL |
| 5120Z | | | AK | | 0-0 | 34-61-12 | D00173A | DED | | | D41563J | | | AK | ALL |
| 5121B | 24 | G2 | AL | | 3-2 | 34-61-12 | D00173A | E07 | | | TB0201Z | 117 | BJ | | ALL |
| 5121R | 24 | G2 | AL | | 0-0 | 34-61-12 | D00173A | D07 | | | TB0201Z | 118 | BJ | | ALL |
| 5121Z | | | AL | | 0-0 | 34-61-12 | D00173A | DED | | | GD01816 | ST.. | 2 | | 001-099 |
| 5121Z | | | AL | | 0-0 | 34-61-12 | GD01816 | ST.. | 2 | | D00173A | DED | | | 115-199 |
| 5122B | 24 | G2 | AN | | 2-10 | 34-61-12 | D00173A | B01 | | | TB0201Z | 101 | BJ | | ALL |
| 5122R | 24 | G2 | AN | | 0-0 | 34-61-12 | D00173A | A01 | | | TB0201Z | 102 | BJ | | ALL |
| 5122Z | | | AN | | 0-0 | 34-61-12 | D00173A | DED | | | GD01814 | ST.. | 2 | | 001-099 |
| 5122Z | | | AN | | 0-0 | 34-61-12 | GD01814 | ST.. | 2 | | D00173A | DED | | | 115-199 |
| 5123B | 24 | G2 | IJ | | 3-6 | 22-24-21 | D41905J | 26 | | | TB0201Z | 119 | BJ | | 001-099 |
| 5123B | 24 | G2 | IJ | | 3-6 | 22-24-21 | TB0201Z | 119 | BJ | | D41905J | 26 | | | 115-199 |
| 5123R | 24 | G2 | IJ | | 0-0 | 22-24-21 | D41905J | 25 | | | TB0201Z | 120 | BJ | | 001-099 |
| 5123R | 24 | G2 | IJ | | 0-0 | 22-24-21 | TB0201Z | 120 | BJ | | D41905J | 25 | | | 115-199 |
| 5123Z | | | IJ | | 0-0 | 22-24-21 | D41905J | 27 | | | GD01816 | ST.. | 2 | | 001-099 |
| 5123Z | | | IJ | | 0-0 | 22-24-21 | GD01816 | ST.. | 2 | | D41905J | 27 | | | 115-199 |
| 5124B | 24 | G2 | AO | | 2-11 | 34-61-12 | D41089J | 8 | | | TB0201Z | 95 | BJ | | ALL |
| 5124R | 24 | G2 | AO | | 0-0 | 34-61-12 | D41089J | 7 | | | TB0201Z | 96 | BJ | | ALL |
| 5124Z | | | AO | | 0-0 | 34-61-12 | D41089J | 9 | | | GD01813 | ST.. | 2 | | ALL |
| 5125B | 24 | G2 | AP | | 2-10 | 34-61-12 | D00173A | E01 | | | TB0201Z | 95 | BJ | | ALL |
| 5125R | 24 | G2 | AP | | 0-0 | 34-61-12 | D00173A | D01 | | | TB0201Z | 96 | BJ | | ALL |
| 5125Z | | | AP | | 0-0 | 34-61-12 | D00173A | DED | | | GD01813 | ST.. | 2 | | 001-099 |
| 5125Z | | | AP | | 0-0 | 34-61-12 | GD01813 | ST.. | 2 | | D00173A | DED | | | 115-199 |
| 5126B | 24 | G2 | AR | | 2-10 | 34-61-12 | D00173A | E15 | | | TB0201Y | C097 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 41

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5126R | 24 | G2 | AR | | 0-0 | 34-61-12 | D00173A | D15 | | | TB0201Y | C098 | BJ | | ALL |
| 5126Z | | | AR | | 0-0 | 34-61-12 | D00173A | DED | | | GD01813 | ST.. | 2 | | 001-099 |
| 5126Z | | | AR | | 0-0 | 34-61-12 | GD01813 | ST.. | 2 | | D00173A | DED | | | 115-199 |
| 5127B | 24 | G2 | AQ | | 2-8 | 34-61-12 | D41339J | 4 | | | TB0201Y | C097 | BJ | | ALL |
| 5127R | 24 | G2 | AQ | | 0-0 | 34-61-12 | D41339J | 3 | | | TB0201Y | C098 | BJ | | ALL |
| 5127Z | | | AQ | | 0-0 | 34-61-12 | D41339J | 5 | | | GD01813 | ST.. | 2 | | ALL |
| 5128B | 24 | G2 | AS | | 2-4 | 34-61-12 | D41563J | 5 | | | TB0201Z | 93 | BJ | | ALL |
| 5128R | 24 | G2 | AS | | 0-0 | 34-61-12 | D41563J | 4 | | | TB0201Z | 94 | BJ | | ALL |
| 5128Z | | | AS | | 0-0 | 34-61-12 | D41563J | 6 | | | GD01813 | ST.. | 2 | | ALL |
| 5129B | 24 | G2 | AT | | 2-10 | 34-61-12 | D00173A | B03 | | | TB0201Z | 93 | BJ | | ALL |
| 5129R | 24 | G2 | AT | | 0-0 | 34-61-12 | D00173A | A03 | | | TB0201Z | 94 | BJ | | ALL |
| 5129Z | | | AT | | 0-0 | 34-61-12 | D00173A | DED | | | GD01813 | ST.. | 2 | | 001-099 |
| 5129Z | | | AT | | 0-0 | 34-61-12 | GD01813 | ST.. | 2 | | D00173A | DED | | | 115-199 |
| 5130B | 24 | G2 | GE | | 4-3 | 22-15-11 | D00035B | F02 | | | D41091J | 30 | | | 001-099 |
| 5130B | 24 | G2 | GE | | 4-3 | 22-15-11 | D41091J | 30 | | | D00035B | F02 | | | 115-199 |
| 5130R | 24 | G2 | GE | | 0-0 | 22-15-11 | D00035B | F01 | | | D41091J | 29 | | | 001-099 |
| 5130R | 24 | G2 | GE | | 0-0 | 22-15-11 | D41091J | 29 | | | D00035B | F01 | | | 115-199 |
| 5130Z | | | GE | | 0-0 | 22-15-11 | D00035B | DED | | | D41091J | | | GE | 001-099 |
| 5130Z | | | GE | | 0-0 | 22-15-11 | D41091J | | | GE | D00035B | DED | | | 115-199 |
| 5131B | 24 | G2 | GF | | 3-3 | 22-15-11 | D00035A | E01 | | | D41391J | 20 | | | 001-099 |
| 5131B | 24 | G2 | GF | | 3-3 | 22-15-11 | D41391J | 20 | | | D00035A | E01 | | | 115-199 |
| 5131R | 24 | G2 | GF | | 0-0 | 22-15-11 | D00035A | D01 | | | D41391J | 19 | | | 001-099 |
| 5131R | 24 | G2 | GF | | 0-0 | 22-15-11 | D41391J | 19 | | | D00035A | D01 | | | 115-199 |
| 5131Z | | | GF | | 0-0 | 22-15-11 | D00035A | DED | | | D41391J | | | GF | 001-099 |
| 5131Z | | | GF | | 0-0 | 22-15-11 | D41391J | | | GF | D00035A | DED | | | 115-199 |
| 5132B | 24 | G2 | GG | | 2-11 | 22-15-11 | D00035B | F03 | | | D41595J | 46 | | | 001-099 |
| 5132B | 24 | G2 | GG | | 2-11 | 22-15-11 | D41595J | 46 | | | D00035B | F03 | | | 115-199 |
| 5132R | 24 | G2 | GG | | 0-0 | 22-15-11 | D00035B | E03 | | | D41595J | 45 | | | 001-099 |
| 5132R | 24 | G2 | GG | | 0-0 | 22-15-11 | D41595J | 45 | | | D00035B | E03 | | | 115-199 |
| 5132Z | | | GG | | 0-0 | 22-15-11 | D00035B | DED | | | D41595J | | | GG | 001-099 |
| 5132Z | | | GG | | 0-0 | 22-15-11 | D41595J | | | GG | D00035B | DED | | | 115-199 |
| 5133B | 24 | G2 | GH | | 4-3 | 22-15-11 | D00035A | H03 | | | D41745J | 2 | | | 001-099 |
| 5133B | 24 | G2 | GH | | 4-3 | 22-15-11 | D41745J | 2 | | | D00035A | H03 | | | 115-199 |
| 5133R | 24 | G2 | GH | | 0-0 | 22-15-11 | D00035A | G03 | | | D41745J | 1 | | | 001-099 |
| 5133R | 24 | G2 | GH | | 0-0 | 22-15-11 | D41745J | 1 | | | D00035A | G03 | | | 115-199 |
| 5133Z | | | GH | | 0-0 | 22-15-11 | D00035A | DED | | | D41745J | | | GH | 001-099 |
| 5133Z | | | GH | | 0-0 | 22-15-11 | D41745J | | | GH | D00035A | DED | | | 115-199 |
| 5134B | 24 | G2 | FN | | 3-4 | 34-22-38 | D41563J | 48 | | | TB0201Z | 49 | BJ | | 001-099 |
| 5134B | 24 | Y2 | FN | | 5-0 | 34-22-38 | D43023J | 25 | | | TB0201Z | 49 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 42

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 5134R | 24 | G2 | FN | 0-0 | 34-22-38 | D41563J | 47 | | | | TB0201Z | 50 | BJ | | 001-099 | |
| 5134R | 24 | Y2 | FN | 0-0 | 34-22-38 | D43023J | 24 | | | | TB0201Z | 50 | BJ | | 115-199 | |
| 5134Z | | | FN | 0-0 | 34-22-38 | D41563J | 49 | | | | GD01807 | ST.. | 2 | | 001-099 | |
| 5134Z | | | FN | 0-0 | 34-22-38 | D43023J | 26 | | | | GD01807 | ST.. | 2 | | 115-199 | |
| 5137B | 24 | G2 | KU | 2-0 | 34-25-11 | D41093J | 30 | | | | TB0201Y | A071 | BJ | | 001, 003-099 | |
| 5137B | 24 | G2 | IG | 2-0 | 34-25-11 | D41093J | 30 | | | | TB0201Y | A071 | BJ | | 115-199 | |
| 5137R | 24 | G2 | KU | 0-0 | 34-25-11 | D41093J | 29 | | | | TB0201Y | A072 | BJ | | 001, 003-099 | |
| 5137R | 24 | G2 | IG | 0-0 | 34-25-11 | D41093J | 29 | | | | TB0201Y | A072 | BJ | | 115-199 | |
| 5137Z | | | KU | 0-0 | 34-25-11 | D41093J | 28 | | | | GD01810 | ST.. | 2 | | 001, 003-099 | |
| 5137Z | | | IG | 0-0 | 34-25-11 | D41093J | 28 | | | | GD01810 | ST.. | 2 | | 115-199 | |
| 5138B | 24 | G2 | IH | 2-9 | 34-22-19 | D00081E | B13 | | | | TB0201Y | A071 | BJ | | 001, 003-099, 115-199 | |
| 5138B | 22 | GU | IH | 4-0 | 34-25-12 | D00081E | B13 | | | | TB0201Y | A071 | BJ | | 002 | |
| 5138R | 24 | G2 | IH | 0-0 | 34-22-19 | D00081E | A13 | | | | TB0201Y | A072 | BJ | | 001, 003-099, 115-199 | |
| 5138R | 22 | GU | IH | 0-0 | 34-25-12 | D00081E | A13 | | | | TB0201Y | A072 | BJ | | 002 | |
| 5138Z | | | IH | 0-0 | 34-22-19 | D00081E | DED | | | | GD01810 | ST.. | 2 | | 001, 003-099, 115-199 | |
| 5138Z | | | IH | 0-0 | 34-25-12 | D00081E | DED | | | | GD01810 | ST.. | 2 | | 002 | |
| 5139B | 24 | G2 | AM | 3-1 | 22-12-31 | D41905J | 31 | | | | TB0201Z | 103 | BJ | | ALL | |
| 5139R | 24 | G2 | AM | 0-0 | 22-12-31 | D41905J | 30 | | | | TB0201Z | 104 | BJ | | ALL | |
| 5139Z | | | AM | 0-0 | 22-12-31 | D41905J | 32 | | | | GD01814 | ST.. | 2 | | ALL | |
| 5140B | 24 | G2 | BQ | 3-5 | 34-22-83 | D42011J | 5 | | | | TB0201Y | C075 | BJ | | 115-199 | |
| 5140R | 24 | G2 | BQ | 0-0 | 34-22-83 | D42011J | 4 | | | | TB0201Y | C076 | BJ | | 115-199 | |
| 5140Z | | | BQ | 0-0 | 34-22-83 | D42011J | 6 | | | | GD01810 | ST.. | 2 | | 115-199 | |
| 5141B | 24 | G2 | PJ | 3-4 | 31-31-43 | D43003J | 35 | | | | TB0201Z | 73 | BJ | | 001-099 | |
| 5141B | 24 | G2 | EN | 2-8 | 31-31-22 | D41093J | 32 | | | | TB0201Z | 55 | BJ | | 115-199 | |
| 5141R | 24 | G2 | PJ | 0-0 | 31-31-43 | D43003J | 34 | | | | TB0201Z | 74 | BJ | | 001-099 | |
| 5141R | 24 | G2 | EN | 0-0 | 31-31-22 | D41093J | 31 | | | | TB0201Z | 56 | BJ | | 115-199 | |
| 5141Z | | | PJ | 0-0 | 31-31-43 | D43003J | 36 | | | | GD01810 | ST.. | 2 | | 001-099 | |
| 5141Z | | | EN | 0-0 | 31-31-22 | D41093J | 33 | | | | GD01807 | ST.. | 2 | | 115-199 | |
| 5142B | 24 | G2 | EZ | 2-8 | 31-31-42 | D41093J | 12 | | | | TB0201Z | 49 | BJ | | 001-099 | |
| 5142B | 24 | G2 | EZ | 2-6 | 31-31-22 | D41093J | 54 | | | | TB0201Z | 79 | BJ | | 115-199 | |
| 5142R | 24 | G2 | EZ | 0-0 | 31-31-42 | D41093J | 11 | | | | TB0201Z | 50 | BJ | | 001-099 | |
| 5142R | 24 | G2 | EZ | 0-0 | 31-31-22 | D41093J | 53 | | | | TB0201Z | 80 | BJ | | 115-199 | |
| 5142Z | | | EZ | 0-0 | 31-31-42 | D41093J | 13 | | | | GD01807 | ST.. | 2 | | 001-099 | |
| 5142Z | | | EZ | 0-0 | 31-31-22 | D41093J | 52 | | | | GD01811 | ST.. | 2 | | 115-199 | |
| 5143B | 24 | G2 | HD | 4-10 | 22-12-31 | D41391J | 39 | | | | TB0201Z | 115 | BJ | | ALL | |
| 5143R | 24 | G2 | HD | 0-0 | 22-12-31 | D41391J | 37 | | | | TB0201Z | 116 | BJ | | ALL | |
| 5143Z | | | HD | 0-0 | 22-12-31 | D41391J | 38 | | | | GD01815 | ST.. | 2 | | ALL | |
| 5149B | 24 | G2 | HJ | 3-6 | 34-16-11 | D41905J | 8 | | | | TB0201Z | 115 | BJ | | ALL | |
| 5149R | 24 | G2 | HJ | 0-0 | 34-16-11 | D41905J | 7 | | | | TB0201Z | 116 | BJ | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 43

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | FT-IN | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5149Z | | | | HJ | 0-0 | 34-16-11 | D41905J | 9 | | | GD01815 | ST.. | 2 | | ALL |
| 5151B | 24 | G2 | | IM | 3-1 | 34-21-21 | D41339J | 22 | | | TB0201Z | 119 | BJ | | ALL |
| 5151R | 24 | G2 | | IM | 0-0 | 34-21-21 | D41339J | 21 | | | TB0201Z | 120 | BJ | | ALL |
| 5151Z | | | | IM | 0-0 | 34-21-21 | D41339J | 23 | | | GD01815 | ST.. | 2 | | ALL |
| 5152B | 24 | G2 | | KD | 3-1 | 34-61-15 | D41905J | 40 | | | TB0201Z | 103 | BJ | | 001-099 |
| 5152B | 24 | G2 | | KD | 3-1 | 34-61-15 | D41905J | 40 | | | TB0201Z | 112 | BJ | | 115-199 |
| 5152R | 24 | G2 | | KD | 0-0 | 34-61-15 | D41905J | 39 | | | TB0201Z | 104 | BJ | | 001-099 |
| 5152R | 24 | G2 | | KD | 0-0 | 34-61-15 | D41905J | 39 | | | TB0201Z | 113 | BJ | | 115-199 |
| 5152Z | | | | KD | 0-0 | 34-61-15 | D41905J | 41 | | | GD01814 | ST.. | 2 | | ALL |
| 5153B | 24 | G2 | | KE | 2-6 | 34-61-15 | D41905J | 42 | | | TB0201Y | A037 | BJ | | ALL |
| 5153R | 24 | G2 | | KE | 0-0 | 34-61-15 | D41905J | 43 | | | TB0201Y | A038 | BJ | | ALL |
| 5153Z | | | | KE | 0-0 | 34-61-15 | D41905J | 44 | | | GD01805 | ST.. | 2 | | ALL |
| 5154B | 24 | G2 | | KF | 2-2 | 34-61-25 | D41339J | 32 | | | TB0201Z | 79 | BJ | | ALL |
| 5154R | 24 | G2 | | KF | 0-0 | 34-61-25 | D41339J | 31 | | | TB0201Z | 80 | BJ | | ALL |
| 5154Z | | | | KF | 0-0 | 34-61-25 | D41339J | 33 | | | GD01811 | ST.. | 2 | | ALL |
| 5158B | 24 | G2 | | PC | 3-1 | 27-32-11 | D41905J | 51 | | | TB0201Z | 103 | BJ | | 001-099 |
| 5158R | 24 | G2 | | PC | 0-0 | 27-32-11 | D41905J | 50 | | | TB0201Z | 104 | BJ | | 001-099 |
| 5158Z | | | | PC | 0-0 | 27-32-11 | D41905J | 52 | | | GD01814 | ST.. | 2 | | 001-099 |
| 5160B | 24 | G2 | | NB | 3-3 | 34-45-02 | D41905J | 17 | | | D01583E | K15 | | | 001-099 |
| 5160B | 24 | G2 | | NB | 3-7 | 34-45-02 | D43003J | 35 | | | D01583E | K15 | | | 115-199 |
| 5160R | 24 | G2 | | NB | 0-0 | 34-45-02 | D41905J | 16 | | | D01583E | J15 | | | 001-099 |
| 5160R | 24 | G2 | | NB | 0-0 | 34-45-02 | D43003J | 34 | | | D01583E | J15 | | | 115-199 |
| 5160Z | | | | NB | 0-0 | 34-45-02 | D41905J | | | NB | D01583E | DED | | | 001-099 |
| 5160Z | | | | NB | 0-0 | 34-45-02 | D43003J | | | NB | D01583E | DED | | | 115-199 |
| 5161B | 24 | G2 | | NC | 3-3 | 34-45-02 | D41905J | 54 | | | D01583E | G14 | | | 001-099 |
| 5161B | 24 | G2 | | NC | 3-7 | 34-45-02 | D43003J | 38 | | | D01583E | G14 | | | 115-199 |
| 5161R | 24 | G2 | | NC | 0-0 | 34-45-02 | D41905J | 53 | | | D01583E | F14 | | | 001-099 |
| 5161R | 24 | G2 | | NC | 0-0 | 34-45-02 | D43003J | 37 | | | D01583E | F14 | | | 115-199 |
| 5161Z | | | | NC | 0-0 | 34-45-02 | D41905J | | | NC | D01583E | DED | | | 001-099 |
| 5161Z | | | | NC | 0-0 | 34-45-02 | D43003J | | | NC | D01583E | DED | | | 115-199 |
| 5162B | 24 | G2 | | ND | 3-8 | 34-45-02 | D41339J | 43 | | | D01583E | B14 | | | 001-099 |
| 5162B | 24 | G2 | | ND | 3-8 | 34-45-02 | D41339J | 7 | | | D01583E | B14 | | | 115-199 |
| 5162R | 24 | G2 | | ND | 0-0 | 34-45-02 | D41339J | 42 | | | D01583E | A14 | | | 001-099 |
| 5162R | 24 | G2 | | ND | 0-0 | 34-45-02 | D41339J | 6 | | | D01583E | A14 | | | 115-199 |
| 5162Z | | | | ND | 0-0 | 34-45-02 | D41339J | | | ND | D01583E | DED | | | ALL |
| 5163B | 24 | G2 | | NE | 3-8 | 34-45-02 | D41339J | 46 | | | D01583E | J14 | | | 001-099 |
| 5163B | 24 | G2 | | NE | 3-8 | 34-45-02 | D41339J | 10 | | | D01583E | J14 | | | 115-199 |
| 5163R | 24 | G2 | | NE | 0-0 | 34-45-02 | D41339J | 45 | | | D01583E | H14 | | | 001-099 |
| 5163R | 24 | G2 | | NE | 0-0 | 34-45-02 | D41339J | 9 | | | D01583E | H14 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 44

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5163Z | | | | NE | 0-0 | 34-45-02 | D41339J | | | | NE | D01583E | DED | | ALL |
| 5164B | 24 | G2 | | NF | 3-8 | 34-45-02 | D41339J | 49 | | | | D01583E | B07 | | 001-099 |
| 5164B | 24 | G2 | | NF | 3-7 | 34-45-02 | D43003J | 18 | | | | D01583E | B07 | | 115-199 |
| 5164R | 24 | G2 | | NF | 0-0 | 34-45-02 | D41339J | 48 | | | | D01583E | A07 | | 001-099 |
| 5164R | 24 | G2 | | NF | 0-0 | 34-45-02 | D43003J | 17 | | | | D01583E | A07 | | 115-199 |
| 5164Z | | | | NF | 0-0 | 34-45-02 | D41339J | | | | NF | D01583E | DED | | 001-099 |
| 5164Z | | | | NF | 0-0 | 34-45-02 | D43003J | | | | NF | D01583E | DED | | 115-199 |
| 5165B | 24 | G2 | | NG | 2-10 | 34-45-02 | D01583E | J13 | | | | TB0201Z | 47 | BJ | ALL |
| 5165R | 24 | G2 | | NG | 0-0 | 34-45-02 | D01583E | H13 | | | | TB0201Z | 48 | BJ | ALL |
| 5165Z | | | | NG | 0-0 | 34-45-02 | D01583E | DED | | | | GD01807 | ST.. | 2 | ALL |
| 5167B | 24 | GL | | NH | 3-4 | 34-45-02 | D41429J | 51 | | | | D01583E | G03 | | ALL |
| 5167R | 24 | GL | | NH | 0-0 | 34-45-02 | D41429J | 50 | | | | D01583E | F03 | | ALL |
| 5168B | 24 | G2 | | NI | 3-8 | 34-45-02 | D41339J | 52 | | | | D01583F | E03 | | 001-099 |
| 5168B | 24 | G2 | | NI | 3-8 | 34-45-02 | D41339J | 52 | | | | D01583E | E03 | | 115-199 |
| 5168R | 24 | G2 | | NI | 0-0 | 34-45-02 | D41339J | 51 | | | | D01583F | D03 | | 001-099 |
| 5168R | 24 | G2 | | NI | 0-0 | 34-45-02 | D41339J | 51 | | | | D01583E | D03 | | 115-199 |
| 5168Z | | | | NI | 0-0 | 34-45-02 | D41339J | | | | NI | D01583F | DED | | 001-099 |
| 5168Z | | | | NI | 0-0 | 34-45-02 | D41339J | | | | NI | D01583E | DED | | 115-199 |
| 5170B | 24 | G2 | | IL | 4-8 | 34-13-11 | D42011J | 26 | | | | TB0201Z | 9 | BJ | ALL |
| 5170R | 24 | G2 | | IL | 0-0 | 34-13-11 | D42011J | 25 | | | | TB0201Z | 10 | BJ | ALL |
| 5170Z | | | | IL | 0-0 | 34-13-11 | D42011J | 27 | | | | GD01802 | ST.. | 2 | ALL |
| 5171B | 24 | G2 | | JR | 2-10 | 22-33-11 | D41905J | 34 | | | | TB0201Y | C030 | BJ | 001-099 |
| 5171B | 24 | G2 | | JM | 2-10 | 22-33-11 | D41905J | 34 | | | | TB0201Y | C030 | BJ | 115-199 |
| 5171R | 24 | G2 | | JR | 0-0 | 22-33-11 | D41905J | 33 | | | | TB0201Y | A030 | BJ | 001-099 |
| 5171R | 24 | G2 | | JM | 0-0 | 22-33-11 | D41905J | 33 | | | | TB0201Y | A030 | BJ | 115-199 |
| 5171Z | | | | JR | 0-0 | 22-33-11 | D41905J | 35 | | | | GD01805 | ST.. | 2 | 001-099 |
| 5171Z | | | | JM | 0-0 | 22-33-11 | D41905J | 35 | | | | GD01805 | ST.. | 2 | 115-199 |
| 5172B | 24 | G2 | | JS | 3-6 | 34-61-14 | D41089J | 11 | | | | TB0201Y | C030 | BJ | ALL |
| 5172R | 24 | G2 | | JS | 0-0 | 34-61-14 | D41089J | 10 | | | | TB0201Y | A030 | BJ | ALL |
| 5172Z | | | | JS | 0-0 | 34-61-14 | D41089J | 12 | | | | GD01805 | ST.. | 2 | ALL |
| 5173B | 24 | G2 | | KP | 2-8 | 34-46-12 | D41429J | 18 | | | | TB0201Z | 49 | BJ | 001-099 |
| 5173B | 24 | G2 | | KP | 2-8 | 34-46-12 | D41429J | 54 | | | | TB0201Z | 49 | BJ | 115-199 |
| 5173R | 24 | G2 | | KP | 0-0 | 34-46-12 | D41429J | 17 | | | | TB0201Z | 50 | BJ | 001-099 |
| 5173R | 24 | G2 | | KP | 0-0 | 34-46-12 | D41429J | 53 | | | | TB0201Z | 50 | BJ | 115-199 |
| 5173Z | | | | KP | 0-0 | 34-46-12 | D41429J | 19 | | | | GD01807 | ST.. | 2 | 001-099 |
| 5173Z | | | | KP | 0-0 | 34-46-12 | D41429J | 55 | | | | GD01807 | ST.. | 2 | 115-199 |
| 5176B | 24 | G2 | | KV | 3-10 | 34-22-19 | D00081D | K01 | | | | D41601J | 46 | | ALL |
| 5176R | 24 | G2 | | KV | 0-0 | 34-22-19 | D00081D | J01 | | | | D41601J | 45 | | ALL |
| 5176Z | | | | KV | 0-0 | 34-22-19 | D00081D | DED | | | | D41601J | | KV | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 45

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5177B | 24 | G2 | KW | | 3-7 | 34-22-19 | D00081A | B07 | | | D41563J | 52 | | | ALL |
| 5177R | 24 | G2 | KW | | 0-0 | 34-22-19 | D00081A | A07 | | | D41563J | 51 | | | ALL |
| 5177Z | | | KW | | 0-0 | 34-22-19 | D00081A | DED | | | D41563J | | | KW | ALL |
| 5178B | 24 | G2 | KX | | 3-5 | 34-22-29 | D41093J | 54 | | | TB0201Z | 117 | BJ | | 001-099 |
| 5178B | 24 | G2 | KU | | 3-5 | 34-22-29 | D41093J | 40 | | | TB0201Z | 117 | BJ | | 115-199 |
| 5178R | 24 | G2 | KX | | 0-0 | 34-22-29 | D41093J | 53 | | | TB0201Z | 118 | BJ | | 001-099 |
| 5178R | 24 | G2 | KU | | 0-0 | 34-22-29 | D41093J | 39 | | | TB0201Z | 118 | BJ | | 115-199 |
| 5178Z | | | KX | | 0-0 | 34-22-29 | D41093J | 55 | | | GD01816 | ST.. | 2 | | 001-099 |
| 5178Z | | | KU | | 0-0 | 34-22-29 | D41093J | 41 | | | GD01816 | ST.. | 2 | | 115-199 |
| 5181B | 24 | G2 | KY | | 2-10 | 34-22-18 | D00081A | H06 | | | TB0201Y | C063 | BJ | | 115-199 |
| 5181R | 24 | G2 | KY | | 0-0 | 34-22-18 | D00081A | G06 | | | TB0201Y | A063 | BJ | | 115-199 |
| 5181Z | | | KY | | 0-0 | 34-22-18 | D00081A | DED | | | GD01811 | ST.. | 2 | | 115-199 |
| 5182B | 24 | G2 | KZ | | 3-5 | 34-22-18 | D41831J | 14 | | | TB0201Y | C063 | BJ | | 115-199 |
| 5182R | 24 | G2 | KZ | | 0-0 | 34-22-18 | D41831J | 13 | | | TB0201Y | A063 | BJ | | 115-199 |
| 5182Z | | | KZ | | 0-0 | 34-22-18 | D41831J | 15 | | | GD01811 | ST.. | 2 | | 115-199 |
| 5183B | 24 | G2 | LA | | 3-10 | 34-22-18 | D00081D | H06 | | | D41601J | 54 | | | 115-199 |
| 5183R | 24 | G2 | LA | | 0-0 | 34-22-18 | D00081D | G06 | | | D41601J | 53 | | | 115-199 |
| 5183Z | | | LA | | 0-0 | 34-22-18 | D00081D | DED | | | D41601J | | | LA | 115-199 |
| 5184B | 24 | G2 | LB | | 3-8 | 34-22-38 | D41595J | 20 | | | TB0201Y | C063 | BJ | | 115-199 |
| 5184R | 24 | G2 | LB | | 0-0 | 34-22-38 | D41595J | 19 | | | TB0201Y | A063 | BJ | | 115-199 |
| 5184Z | | | LB | | 0-0 | 34-22-38 | D41595J | 21 | | | GD01810 | ST.. | 2 | | 115-199 |
| 5186B | 24 | G2 | LF | | 4-10 | 34-22-28 | D41595J | 54 | | | D42011J | 51 | | | 115-199 |
| 5186R | 24 | G2 | LF | | 0-0 | 34-22-28 | D41595J | 53 | | | D42011J | 50 | | | 115-199 |
| 5186Z | | | LF | | 0-0 | 34-22-28 | D41595J | 55 | | | D42011J | | | LF | 115-199 |
| 5187B | 24 | G2 | NJ | | 4-9 | 34-45-01 | D42065J | 43 | | | D01583E | D13 | | | 001-002 |
| 5187B | 24 | G2 | NJ | | 4-9 | 34-45-01 | D42065J | 34 | | | D01583E | D13 | | | 115-199 |
| 5187R | 24 | G2 | NJ | | 0-0 | 34-45-01 | D42065J | 42 | | | D01583E | C13 | | | 001-002 |
| 5187R | 24 | G2 | NJ | | 0-0 | 34-45-01 | D42065J | 33 | | | D01583E | C13 | | | 115-199 |
| 5187Z | | | NJ | | 0-0 | 34-45-01 | D42065J | | | NJ | D01583E | DED | | | 001-002, 115-199 |
| 5188B | 24 | G2 | NK | | 4-4 | 34-45-01 | D42065J | 49 | | | TB0201Z | 23 | BJ | | 001-099 |
| 5188B | 24 | G2 | NK | | 4-4 | 34-45-01 | D42065J | 40 | | | TB0201Z | 23 | BJ | | 115-199 |
| 5188R | 24 | G2 | NK | | 0-0 | 34-45-01 | D42065J | 48 | | | TB0201Z | 24 | BJ | | 001-099 |
| 5188R | 24 | G2 | NK | | 0-0 | 34-45-01 | D42065J | 39 | | | TB0201Z | 24 | BJ | | 115-199 |
| 5188Z | | | NK | | 0-0 | 34-45-01 | D42065J | 50 | | | GD01804 | ST.. | 2 | | 001-099 |
| 5188Z | | | NK | | 0-0 | 34-45-01 | D42065J | 41 | | | GD01804 | ST.. | 2 | | 115-199 |
| 5189B | 24 | G2 | NL | | 3-10 | 34-45-01 | D42013J | 43 | | | D01583E | B13 | | | 001-002, 115-199 |
| 5189R | 24 | G2 | NL | | 0-0 | 34-45-01 | D42013J | 42 | | | D01583E | A13 | | | 001-002, 115-199 |
| 5189Z | | | NL | | 0-0 | 34-45-01 | D42013J | | | NL | D01583E | DED | | | 001-002, 115-199 |
| 5190B | 24 | G2 | NN | | 2-9 | 34-45-01 | D42013J | 49 | | | TB0201Z | 33 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 46

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5190R | 24 | G2 | NN | | 0-0 | 34-45-01 | D42013J | 48 | | | TB0201Z | 34 | BJ | | ALL |
| 5190Z | | | NN | | 0-0 | 34-45-01 | D42013J | 50 | | | GD01805 | ST.. | 2 | *1 | ALL |
| 5191B | 24 | G2 | NP | | 2-8 | 34-45-01 | D41391J | 49 | | | TB0201Z | 33 | BJ | | ALL |
| 5191R | 24 | G2 | NP | | 0-0 | 34-45-01 | D41391J | 48 | | | TB0201Z | 34 | BJ | | ALL |
| 5191Z | | | NP | | 0-0 | 34-45-01 | D41391J | 50 | | | GD01805 | ST.. | 2 | *1 | ALL |
| 5192B | 24 | G2 | NR | | 3-0 | 34-45-01 | D41093J | 40 | | | TB0201Z | 33 | BJ | | 001-099 |
| 5192B | 24 | G2 | NR | | 2-6 | 34-45-01 | D43003J | 47 | | | TB0201Z | 33 | BJ | | 115-199 |
| 5192R | 24 | G2 | NR | | 0-0 | 34-45-01 | D41093J | 39 | | | TB0201Z | 34 | BJ | | 001-099 |
| 5192R | 24 | G2 | NR | | 0-0 | 34-45-01 | D43003J | 46 | | | TB0201Z | 34 | BJ | | 115-199 |
| 5192Z | | | NR | | 0-0 | 34-45-01 | D41093J | 41 | | | GD01805 | ST.. | 2 | *2 | 001-099 |
| 5192Z | | | NR | | 0-0 | 34-45-01 | D43003J | 48 | | | GD01805 | ST.. | 2 | *2 | 115-199 |
| 5193B | 24 | G2 | NS | | 3-7 | 34-45-01 | TB0201Z | 33 | BJ | | D00081A | K09 | | | 001-099 |
| 5193B | 24 | G2 | NS | | 3-7 | 34-45-01 | TB0201Z | 33 | BJ | | D00081A | REF | VP | | 115-199 |
| 5193R | 24 | G2 | NS | | 0-0 | 34-45-01 | TB0201Z | 34 | BJ | | D00081A | J09 | | | 001-099 |
| 5193R | 24 | G2 | NS | | 0-0 | 34-45-01 | TB0201Z | 34 | BJ | | D00081A | REF | VP | | 115-199 |
| 5193Z | | | NS | | 0-0 | 34-45-01 | GD01805 | ST.. | 2 | *2 | D00081A | DED | | | ALL |
| 5194B | 24 | G2 | NT | | 3-1 | 34-45-01 | D01583E | D07 | | | TB0201Z | 33 | BJ | | ALL |
| 5194R | 24 | G2 | NT | | 0-0 | 34-45-01 | D01583E | C07 | | | TB0201Z | 34 | BJ | | ALL |
| 5194Z | | | NT | | 0-0 | 34-45-01 | D01583E | DED | | | GD01805 | ST.. | 2 | | ALL |
| 5195B | 24 | G2 | NU | | 3-1 | 34-45-01 | D01583E | H07 | | | TB0201Z | 23 | BJ | | ALL |
| 5195R | 24 | G2 | NU | | 0-0 | 34-45-01 | D01583E | G07 | | | TB0201Z | 24 | BJ | | ALL |
| 5195Z | | | NU | | 0-0 | 34-45-01 | D01583E | DED | | | GD01804 | ST.. | 2 | | ALL |
| 5196B | 24 | G2 | NV | | 3-3 | 34-45-01 | D41339J | 40 | | | TB0201Z | 23 | BJ | | ALL |
| 5196R | 24 | G2 | NV | | 0-0 | 34-45-01 | D41339J | 39 | | | TB0201Z | 24 | BJ | | ALL |
| 5196Z | | | NV | | 0-0 | 34-45-01 | D41339J | 41 | | | GD01804 | ST.. | 2 | | ALL |
| 5199B | 24 | G2 | II | | 2-8 | 34-45-01 | D41391J | 2 | | | TB0201Z | 23 | BJ | | 003-099 |
| 5199R | 24 | G2 | II | | 0-0 | 34-45-01 | D41391J | 1 | | | TB0201Z | 24 | BJ | | 003-099 |
| 5199Z | | | II | | 0-0 | 34-45-01 | D41391J | 3 | | | GD01804 | ST.. | 2 | | 003-099 |
| 5206B | 22 | X2 | QB | | 5-0 | 34-61-11 | D41081J | 22 | | | TB0201Z | 93 | BJ | | 115-199 |
| 5206R | 22 | X2 | QB | | 0-0 | 34-61-11 | D41081J | 23 | | | TB0201Z | 94 | BJ | | 115-199 |
| 5206Z | | | QB | | 0-0 | 34-61-11 | D41081J | 18 | | | GD01811 | ST.. | 2 | | 115-199 |
| 5207B | 24 | G2 | IG | | 3-0 | 34-61-11 | D41081J | 20 | | | TB0201Z | 53 | BJ | | 001-099 |
| 5207B | 22 | X2 | HE | | 5-0 | 34-61-11 | D41081J | 20 | | | TB0201Z | 53 | BJ | | 115-199 |
| 5207R | 24 | G2 | IG | | 0-0 | 34-61-11 | D41081J | 19 | | | TB0201Z | 54 | BJ | | 001-099 |
| 5207R | 22 | X2 | HE | | 0-0 | 34-61-11 | D41081J | 19 | | | TB0201Z | 54 | BJ | | 115-199 |
| 5207Z | | | IG | | 0-0 | 34-61-11 | D41081J | 21 | | | GD01807 | ST.. | 2 | | 001-099 |
| 5207Z | | | HE | | 0-0 | 34-61-11 | D41081J | 21 | | | GD01808 | ST.. | 2 | | 115-199 |
| 5208B | 24 | G2 | PB | | 5-2 | 34-61-14 | D41595J | 52 | | | D00173B | E09 | | | 001-099 |
| 5208B | 22 | X2 | PB | | 5-2 | 34-61-14 | D41595J | 52 | | | D00173B | E09 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 47

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|-------------|-----------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | | Splice |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5208R | 24 | G2 | PB | | 0-0 | 34-61-14 | D41595J | 51 | | | | D00173B | D09 | | 001-099 |
| 5208R | 22 | X2 | PB | | 0-0 | 34-61-14 | D41595J | 51 | | | | D00173B | D09 | | 115-199 |
| 5208Z | | | PB | | 0-0 | 34-61-14 | D41595J | | | PB | | D00173B | DED | | ALL |
| 5209B | 22 | X2 | QW | | 5-0 | 34-61-16 | D41081J | 16 | | | | D43023J | 4 | | 115-199 |
| 5209R | 22 | X2 | QW | | 0-0 | 34-61-16 | D41081J | 17 | | | | D43023J | 3 | | 115-199 |
| 5209Z | | | QW | | 0-0 | 34-61-16 | D41081J | | | QW | | D43023J | 5 | | 115-199 |
| 5210B | 22 | X2 | QX | | 4-0 | 34-61-16 | D43023J | 16 | | | | TB0201Z | 112 | BJ | 115-199 |
| 5210R | 22 | X2 | QX | | 0-0 | 34-61-16 | D43023J | 15 | | | | TB0201Z | 113 | BJ | 115-199 |
| 5210Z | | | QX | | 0-0 | 34-61-16 | D43023J | 17 | | | | GD01815 | ST.. | 2 | 115-199 |
| 5211B | 22 | X2 | QY | | 4-0 | 34-61-16 | D43023J | 21 | | | | TB0201Z | 103 | BJ | 115-199 |
| 5211R | 22 | X2 | QY | | 0-0 | 34-61-16 | D43023J | 20 | | | | TB0201Z | 104 | BJ | 115-199 |
| 5211Z | | | QY | | 0-0 | 34-61-16 | D43023J | 22 | | | | GD01815 | ST.. | 2 | 115-199 |
| 5212B | 24 | G2 | PF | | 3-7 | 34-61-24 | D41601J | 54 | | | | TB0201Z | 53 | BJ | 001-099 |
| 5212B | 22 | X2 | PF | | 5-0 | 34-61-24 | D41601J | 36 | | | | TB0201Z | 53 | BJ | 115-199 |
| 5212R | 24 | G2 | PF | | 0-0 | 34-61-24 | D41601J | 53 | | | | TB0201Z | 54 | BJ | 001-099 |
| 5212R | 22 | X2 | PF | | 0-0 | 34-61-24 | D41601J | 35 | | | | TB0201Z | 54 | BJ | 115-199 |
| 5212Z | | | PF | | 0-0 | 34-61-24 | D41601J | 55 | | | | GD01808 | ST.. | 2 | 001-099 |
| 5212Z | | | PF | | 0-0 | 34-61-24 | D41601J | 37 | | | | GD01808 | ST.. | 2 | 115-199 |
| 5213B | 22 | X2 | RJ | | 5-0 | 34-61-26 | D42173J | 2 | | | | D00173B | H09 | | 115-199 |
| 5213R | 22 | X2 | RJ | | 0-0 | 34-61-26 | D42173J | 1 | | | | D00173B | G09 | | 115-199 |
| 5213Z | | | RJ | | 0-0 | 34-61-26 | D42173J | 3 | | | | D00173B | DED | | 115-199 |
| 5214B | 22 | X2 | RR | | 5-0 | 34-61-26 | D42173J | 5 | | | | TB0201Z | 79 | BJ | 115-199 |
| 5214R | 22 | X2 | RR | | 0-0 | 34-61-26 | D42173J | 4 | | | | TB0201Z | 80 | BJ | 115-199 |
| 5214Z | | | RR | | 0-0 | 34-61-26 | D42173J | 6 | | | | GD01811 | ST.. | 2 | 115-199 |
| 5215B | 22 | X2 | RS | | 4-0 | 34-61-26 | D42173J | 8 | | | | TB0201Z | 103 | BJ | 115-199 |
| 5215R | 22 | X2 | RS | | 0-0 | 34-61-26 | D42173J | 7 | | | | TB0201Z | 104 | BJ | 115-199 |
| 5215Z | | | RS | | 0-0 | 34-61-26 | D42173J | 9 | | | | GD01814 | ST.. | 2 | 115-199 |
| 5220B | 22 | X2 | QV | | 5-0 | 34-61-14 | D41817J | 24 | | | | D00173B | B05 | | 115-199 |
| 5220R | 22 | X2 | QV | | 0-0 | 34-61-14 | D41817J | 23 | | | | D00173B | A05 | | 115-199 |
| 5220Z | | | QV | | 0-0 | 34-61-14 | D41817J | | | QV | | D00173B | DED | | 115-199 |
| 5221B | 22 | X2 | QZ | | 5-0 | 34-61-24 | D41601J | 51 | | | | TB0201Y | C30 | BJ | 115-199 |
| 5221R | 22 | X2 | QZ | | 0-0 | 34-61-24 | D41601J | 50 | | | | TB0201Y | A30 | BJ | 115-199 |
| 5221Z | | | QZ | | 0-0 | 34-61-24 | D41601J | 1 | | | | GD01805 | ST.. | 2 | 115-199 |
| 5229B | 24 | G2 | PI | | 2-11 | 31-31-43 | D43003J | 32 | | | | TB0201Z | 55 | BJ | 001-099 |
| 5229R | 24 | G2 | PI | | 0-0 | 31-31-43 | D43003J | 31 | | | | TB0201Z | 56 | BJ | 001-099 |
| 5229Z | | | PI | | 0-0 | 31-31-43 | D43003J | 33 | | | | GD01808 | ST.. | 2 | 001-099 |
| 5232B | 22 | GU | MA | | 4-0 | 34-25-12 | D41745J | 14 | | | | TB0201Y | A071 | BJ | 002 |
| 5232R | 22 | GU | MA | | 0-0 | 34-25-12 | D41745J | 13 | | | | TB0201Y | A072 | BJ | 002 |
| 5232Z | | | MA | | 0-0 | 34-25-12 | D41745J | 15 | | | | GD01810 | ST.. | 2 | *1 002 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 48

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | |
| 5234B | 22 | GU | MC | | 5-0 | 34-25-12 | D41238J | 24 | | | TB0201Y | A071 | BJ | | 002 |
| 5234R | 22 | GU | MC | | 0-0 | 34-25-12 | D41238J | 23 | | | TB0201Y | A072 | BJ | | 002 |
| 5234Z | | | MC | | 0-0 | 34-25-12 | D41238J | 25 | | | GD01810 | ST.. | 2 | | 002 |
| 5235B | 22 | GU | MJ | | 6-0 | 34-25-12 | D41238J | 26 | | | D00081D | D02 | | | 002 |
| 5235R | 22 | GU | MJ | | 0-0 | 34-25-12 | D41238J | 27 | | | D00081D | C02 | | | 002 |
| 5235Z | | | MJ | | 0-0 | 34-25-12 | D41238J | | | MJ | D00081D | DED | | | 002 |
| 5236B | 22 | GU | MS | | 5-0 | 34-25-12 | D41745J | 9 | | | D00081A | D02 | | | 002 |
| 5236R | 22 | GU | MS | | 0-0 | 34-25-12 | D41745J | 8 | | | D00081A | C02 | | | 002 |
| 5236Z | | | MS | | 0-0 | 34-25-12 | D41745J | | | MS | D00081A | DED | | | 002 |
| 5244B | 22 | GU | KJ | | 4-9 | 34-58-11 | D41817J | 8 | | | D00173B | B07 | | | 115-199 |
| 5244R | 22 | GU | KJ | | 0-0 | 34-58-11 | D41817J | 1 | | | D00173B | A07 | | | 115-199 |
| 5244Z | | | KJ | | 0-0 | 34-58-11 | D41817J | 31 | | | D00173B | DED | | | 115-199 |
| 5245B | 22 | GU | KL | | 4-9 | 34-58-21 | D41817J | 54 | | | D00173A | B15 | | | 115-199 |
| 5245R | 22 | GU | KL | | 0-0 | 34-58-21 | D41817J | 53 | | | D00173A | A15 | | | 115-199 |
| 5245Z | | | KL | | 0-0 | 34-58-21 | D41817J | 55 | | | D00173A | DED | | | 115-199 |
| 5246B | 22 | GU | QC | | 5-0 | 34-43-14 | D41238J | 17 | | | SM00098 | | 9 | | 002 |
| 5246R | 22 | GU | QC | | 0-0 | 34-43-14 | D41238J | 16 | | | SM00099 | | 9 | | 002 |
| 5246Z | | | QC | | 0-0 | 34-43-14 | D41238J | 18 | | | GD01807 | ST.. | 2 | | 002 |
| 5248B | 22 | GU | KB | | 6-0 | 34-43-14 | D41238J | 14 | | | TB0201Z | 115 | BJ | | 002 |
| 5248R | 22 | GU | KB | | 0-0 | 34-43-14 | D41238J | 13 | | | TB0201Z | 116 | BJ | | 002 |
| 5248Z | | | KB | | 0-0 | 34-43-14 | D41238J | 15 | | | GD01816 | ST.. | 2 | | 002 |
| 5276B | 22 | GU | QJ | | 6-0 | 34-43-15 | D41817J | 27 | | | D41238J | 21 | | | 002 |
| 5276R | 22 | GU | QJ | | 0-0 | 34-43-15 | D41817J | 26 | | | D41238J | 20 | | | 002 |
| 5276Z | | | QJ | | 0-0 | 34-43-15 | D41817J | 28 | | | D41238J | 19 | | | 002 |
| 5280B | 22 | GU | ON | | 6-0 | 34-22-18 | D00081E | B14 | | | D21001J | 28 | | | 002 |
| 5280R | 22 | GU | ON | | 0-0 | 34-22-18 | D00081E | A14 | | | D21001J | 27 | | | 002 |
| 5280Z | | | ON | | 0-0 | 34-22-18 | D00081E | DED | | | D21001J | | | ON | 002 |
| 5281B | 22 | GU | D1 | | 6-0 | 34-46-12 | D41429J | 40 | | | D00081D | D08 | | | 002 |
| 5281R | 22 | GU | D1 | | 0-0 | 34-46-12 | D41429J | 39 | | | D00081D | C08 | | | 002 |
| 5281Z | | | D1 | | 0-0 | 34-46-12 | D41429J | | | D1 | D00081D | DED | | | 002 |
| 5297B | 22 | GU | CZ | | 5-0 | 34-43-11 | D21001J | 17 | | | D41061J | 9 | | | 002 |
| 5297R | 22 | GU | CZ | | 0-0 | 34-43-11 | D21001J | 16 | | | D41061J | 8 | | | 002 |
| 5297Z | | | CZ | | 0-0 | 34-43-11 | D21001J | 18 | | | D41061J | 7 | | | 002 |
| 5312B | 24 | G2 | PK | | 3-5 | 31-31-43 | D43003J | 38 | | | TB0201Z | 75 | BJ | | 001-099 |
| 5312R | 24 | G2 | PK | | 0-0 | 31-31-43 | D43003J | 37 | | | TB0201Z | 76 | BJ | | 001-099 |
| 5312Z | | | PK | | 0-0 | 31-31-43 | D43003J | 39 | | | GD01812 | ST.. | 2 | | 001-099 |
| 5313B | 24 | G2 | PN | | 2-11 | 31-31-43 | D43003J | 29 | | | TB0201Z | 53 | BJ | | 001-009 |
| 5313B | 24 | G2 | PN | | 2-11 | 31-31-43 | D43003J | 29 | | | TB0201Y | A037 | BJ | | 010-099 |
| 5313R | 24 | G2 | PN | | 0-0 | 31-31-43 | D43003J | 28 | | | TB0201Z | 54 | BJ | | 001-009 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 49

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1171 | 286N1171 | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5313R | 24 | G2 | PN | | 0-0 | 31-31-43 | D43003J | 28 | | | TB0201Y | A038 | BJ | | 010-099 |
| 5313Z | | | PN | | 0-0 | 31-31-43 | D43003J | 30 | | | GD01807 | ST.. | 2 | | 001-009 |
| 5313Z | | | PN | | 0-0 | 31-31-43 | D43003J | 30 | | | GD01805 | ST.. | 2 | | 010-099 |
| 5353B | 24 | G2 | SA | | 3-0 | 27-32-11 | D41091J | 4 | | | TB0201Y | C066 | BJ | | 001-099 |
| 5353B | 24 | G2 | SA | | 3-0 | 27-32-11 | D41091J | 4 | | | TB0201Y | A078 | BJ | | 115-199 |
| 5353R | 24 | G2 | SA | | 0-0 | 27-32-11 | D41091J | 3 | | | TB0201Y | A066 | BJ | | 001-099 |
| 5353R | 24 | G2 | SA | | 0-0 | 27-32-11 | D41091J | 3 | | | TB0201Y | A077 | BJ | | 115-199 |
| 5353Z | | | SA | | 0-0 | 27-32-11 | D41091J | 5 | | | TB0201Y | | | SA | ALL |
| 5354B | 24 | G2 | SB | | 3-0 | 27-32-11 | D42175J | 7 | | | TB0201Y | C066 | BJ | | 001-099 |
| 5354B | 24 | G2 | SB | | 3-0 | 27-32-11 | D42175J | 7 | | | TB0201Y | A078 | BJ | | 115-199 |
| 5354R | 24 | G2 | SB | | 0-0 | 27-32-11 | D42175J | 6 | | | TB0201Y | A066 | BJ | | 001-099 |
| 5354R | 24 | G2 | SB | | 0-0 | 27-32-11 | D42175J | 6 | | | TB0201Y | A077 | BJ | | 115-199 |
| 5354Z | | | SB | | 0-0 | 27-32-11 | D42175J | 8 | | | TB0201Y | | | SB | ALL |
| 5355B | 24 | G2 | SC | | 4-0 | 34-12-62 | D42175J | 12 | | | TB0201Z | 9 | BJ | | ALL |
| 5355R | 24 | G2 | SC | | 0-0 | 34-12-62 | D42175J | 11 | | | TB0201Z | 10 | BJ | | ALL |
| 5355Z | | | SC | | 0-0 | 34-12-62 | D42175J | 13 | | | GD01802 | ST.. | 2 | | ALL |
| 8007 | 22 | GA | | | 3-0 | 34-22-16 | D00081B | D02 | | | GD01810 | ST.. | 2 | | 002 |
| 8022 | 22 | GA | | | 5-0 | 34-22-16 | GD01806 | ST.. | 2 | | D00081B | G06 | | | 002 |
| 8026 | 22 | GA | | | 4-0 | 34-22-16 | GD01808 | ST.. | 2 | | D00081B | E06 | | | 002 |
| 8027 | 22 | GA | | | 4-0 | 34-22-16 | GD01808 | ST.. | 2 | | D00081B | K05 | | | 002 |
| 8041 | 22 | GA | | | 4-0 | 34-22-16 | D00081A | A14 | | | GD01808 | ST.. | 2 | | 002 |
| 8046 | 22 | GA | | | 4-0 | 34-22-16 | GD01808 | ST.. | 2 | | D00081B | J02 | | | 002 |
| 8046 | 22 | PA | | | 4-0 | 34-22-16 | D00081B | J02 | | | GD01806 | ST.. | 2 | | 115-199 |
| 8761 | 22 | GA | | | 4-0 | 34-43-14 | SM00098 | | 9 | | TB0201Z | 47 | BJ | | 002 |
| 8762 | 22 | GA | | | 4-0 | 34-43-14 | SM00099 | | 9 | | TB0201Z | 48 | BJ | | 002 |
| A-BL | | | | | 0-0 | 73-21-12 | TB0201A | 5 | | | TB0201Y | A016 | BJ | | ALL |
| A-GR | | | | | 0-0 | 73-21-12 | TB0201A | 5 | | | TB0201Y | A042 | BJ | | ALL |
| A-RD | | | | | 0-0 | 73-21-12 | TB0201A | 5 | | | TB0201Y | A015 | BJ | | ALL |
| A-YL | | | | | 0-0 | 73-21-12 | TB0201A | 5 | | | GD01803 | ST.. | 2 | | ALL |
| B-BL | | | | | 0-0 | 73-21-12 | TB0201A | 7 | | | TB0201Y | A041 | BJ | | ALL |
| B-GR | | | | | 0-0 | 73-21-12 | TB0201A | 7 | | | TB0201Y | C016 | BJ | | ALL |
| B-RD | | | | | 0-0 | 73-21-12 | TB0201A | 7 | | | TB0201Y | C015 | BJ | | ALL |
| B-YL | | | | | 0-0 | 73-21-12 | TB0201A | 7 | | | GD01803 | ST.. | 2 | | ALL |
| FRAA | | | | | 0-0 | 34-22-18 | D41563J | | | CY | D41563J | 37 | | | 001-099 |
| FRAH | | | | | 0-0 | 34-61-11 | D41817J | 20 | | | D41817J | | | AH | 001-099 |
| FRAH | | | | | 1-0 | 34-61-11 | D41817J | | | AH | D41817J | 20 | | | 115-199 |
| FRAI | | | | | 0-0 | 34-61-11 | D41081J | 9 | | | D41081J | | | AI | 001-099 |
| FRAI | | | | | 0-0 | 34-61-11 | D41081J | | | AI | D41081J | 9 | | | 115-199 |
| FRAK | | | | | 0-0 | 34-61-12 | D41563J | 3 | | | D41563J | | | AK | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 50

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1171 | 286N1171 | | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| FRAK | | | | | 0-0 | 34-61-12 | D41563J | | | | AK | D41563J | 3 | | | 115-199 | |
| FRAU | | | | | 0-0 | 34-61-13 | D41601J | | 7 | | | D41601J | | AU | | 001-099 | |
| FRAU | | | | | 0-0 | 34-61-13 | D41601J | | | | AU | D41601J | 7 | | | 115-199 | |
| FRAV | | | | | 0-0 | 34-61-13 | D41601J | | 10 | | | D41601J | | AV | | 001-099 | |
| FRAV | | | | | 0-0 | 34-61-13 | D41601J | | | | AV | D41601J | 10 | | | 115-199 | |
| FRAW | | | | | 0-0 | 34-61-13 | D41601J | | 14 | | | D41601J | | AW | | 001-099 | |
| FRAW | | | | | 0-0 | 34-61-13 | D41601J | | | | AW | D41601J | 14 | | | 115-199 | |
| FRAX | | | | | 0-0 | 34-61-13 | D41601J | | 17 | | | D41601J | | AX | | 001-099 | |
| FRAX | | | | | 0-0 | 34-61-13 | D41601J | | | | AX | D41601J | 17 | | | 115-199 | |
| FRAZ | | | | | 0-0 | 34-61-14 | D41089J | | 15 | | | D41089J | | AZ | | 001-099 | |
| FRAZ | | | | | 0-0 | 34-61-14 | D41089J | | | | AZ | D41089J | 15 | | | 115-199 | |
| FRBA | | | | | 0-0 | 34-61-14 | D42183J | | 5 | | | D42183J | | BA | | 001-099 | |
| FRBA | | | | | 0-0 | 34-61-14 | D42183J | | | | BA | D42183J | 5 | | | 115-199 | |
| FRBD | | | | | 0-0 | 34-61-15 | D42183J | | 8 | | | D42183J | | BD | | 001-099 | |
| FRBD | | | | | 0-0 | 34-61-15 | D42183J | | | | BD | D42183J | 8 | | | 115-199 | |
| FRBI | | | | | 0-0 | 34-61-21 | D41601J | | 20 | | | D41601J | | BI | | ALL | |
| FRBJ | | | | | 0-0 | 34-61-21 | D41601J | | 22 | | | D41601J | | BJ | | ALL | |
| FRBK | | | | | 0-0 | 34-61-21 | D41601J | | 27 | | | D41601J | | BK | | ALL | |
| FRCC | | | | | 0-0 | 22-12-11 | D41091J | | 21 | | | D41091J | | CC | | 001-099 | |
| FRCC | | | | | 0-0 | 22-12-11 | D41091J | | | | CC | D41091J | 21 | | | 115-199 | |
| FRCH | | | | | 0-0 | 22-12-21 | D41745J | | 7 | | | D41745J | | CH | | 001-099 | |
| FRCH | | | | | 1-0 | 22-12-21 | D41745J | | | | CH | D41745J | 7 | | | 115-199 | |
| FRCW | | | | | 0-0 | 34-22-18 | D41601J | | 33 | | | D41601J | | CW | | 001-099 | |
| FRCX | | | | | 0-0 | 34-22-18 | D41391J | | 6 | | | D41391J | | CX | | ALL | |
| FRD1 | | | | | 0-0 | 34-46-12 | D41429J | | 38 | | | D41429J | | D1 | | 002 | |
| FRDH | | | | | 0-0 | 34-22-19 | D41563J | | 40 | | | D41563J | | DH | | ALL | |
| FREW | | | | | 0-0 | 22-41-12 | D41093J | | 3 | | | D41093J | | EW | | ALL | |
| FREX | | | | | 0-0 | 22-41-11 | D41091J | | 42 | | | D41091J | | EX | | ALL | |
| FRFF | | | | | 0-0 | 31-31-22 | D41093J | | 48 | | | D41093J | | FF | | 115-199 | |
| FRFH | | | | | 0-0 | 31-31-42 | D41093J | | | | FH | D41093J | 48 | | | 001-099 | |
| FRFR | | | | | 0-0 | 22-12-31 | D41391J | | 12 | | | D41391J | | FR | | 001-099 | |
| FRFR | | | | | 0-0 | 22-12-31 | D41391J | | | | FR | D41391J | 12 | | | 115-199 | |
| FRFX | | | | | 0-0 | 22-13-11 | D41595J | | 37 | | | D41595J | | FX | | 001-099 | |
| FRFX | | | | | 0-0 | 22-13-11 | D41595J | | | | FX | D41595J | 37 | | | 115-199 | |
| FRGE | | | | | 0-0 | 22-15-11 | D41091J | | 31 | | | D41091J | | GE | | 001-099 | |
| FRGE | | | | | 0-0 | 22-15-11 | D41091J | | | | GE | D41091J | 31 | | | 115-199 | |
| FRGF | | | | | 0-0 | 22-15-11 | D41391J | | 21 | | | D41391J | | GF | | 001-099 | |
| FRGF | | | | | 0-0 | 22-15-11 | D41391J | | | | GF | D41391J | 21 | | | 115-199 | |
| FRGG | | | | | 0-0 | 22-15-11 | D41595J | | 47 | | | D41595J | | GG | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 51

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|---------|------|--------|-------|------|---------|--------|----|------------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1171 | 286N1171 | | | | E2-1 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| FRGG | | | | | 0-0 | 22-15-11 | | D41595J | | | | GG | D41595J | 47 | | 115-199 | |
| FRGH | | | | | 0-0 | 22-15-11 | | D41745J | 3 | | | | D41745J | | GH | 001-099 | |
| FRGH | | | | | 1-0 | 22-15-11 | | D41745J | | | | GH | D41745J | 3 | | 115-199 | |
| FRKV | | | | | 0-0 | 34-22-19 | | D41601J | 47 | | | | D41601J | | KV | ALL | |
| FRKW | | | | | 0-0 | 34-22-19 | | D41563J | 53 | | | | D41563J | | KW | ALL | |
| FRLA | | | | | 0-0 | 34-22-18 | | D41601J | 55 | | | | D41601J | | LA | 115-199 | |
| FRLF | | | | | 0-0 | 34-22-28 | | D42011J | | | LF | | D42011J | 52 | | 115-199 | |
| FRMJ | | | | | 0-0 | 34-25-12 | | D41238J | | | MJ | | D41238J | 28 | | 002 | |
| FRMS | | | | | 0-0 | 34-25-12 | | D41745J | | | MS | | D41745J | 11 | | 002 | |
| FRNA | | | | | 0-0 | 22-13-11 | | D41905J | | | NA | | D41905J | 3 | | 001-099 | |
| FRNA | | | | | 0-0 | 22-13-11 | | D43003J | | | NA | | D43003J | 45 | | 115-199 | |
| FRNB | | | | | 0-0 | 34-45-02 | | D41905J | | | NB | | D41905J | 12 | | 001-099 | |
| FRNB | | | | | 0-0 | 34-45-02 | | D43003J | | | NB | | D43003J | 36 | | 115-199 | |
| FRNC | | | | | 0-0 | 34-45-02 | | D41905J | | | NC | | D41905J | 55 | | 001-099 | |
| FRNC | | | | | 0-0 | 34-45-02 | | D43003J | | | NC | | D43003J | 39 | | 115-199 | |
| FRND | | | | | 0-0 | 34-45-02 | | D41339J | | | ND | | D41339J | 44 | | 001-099 | |
| FRND | | | | | 0-0 | 34-45-02 | | D41339J | | | ND | | D41339J | 8 | | 115-199 | |
| FRNE | | | | | 0-0 | 34-45-02 | | D41339J | | | NE | | D41339J | 47 | | 001-099 | |
| FRNE | | | | | 0-0 | 34-45-02 | | D41339J | | | NE | | D41339J | 11 | | 115-199 | |
| FRNF | | | | | 0-0 | 34-45-02 | | D41339J | | | NF | | D41339J | 50 | | 001-099 | |
| FRNF | | | | | 0-0 | 34-45-02 | | D43003J | | | NF | | D43003J | 19 | | 115-199 | |
| FRNI | | | | | 0-0 | 34-45-02 | | D41339J | | | NI | | D41339J | 53 | | ALL | |
| FRNJ | | | | | 0-0 | 34-45-01 | | D42065J | | | NJ | | D42065J | 44 | | 001-002 | |
| FRNJ | | | | | 0-0 | 34-45-01 | | D42065J | | | NJ | | D42065J | 36 | | 115-199 | |
| FRNL | | | | | 0-0 | 34-45-01 | | D42013J | | | NL | | D42013J | 44 | | 001-002, 115-199 | |
| FRON | | | | | 0-0 | 34-22-18 | | D21001J | 29 | | | | D21001J | | ON | 002 | |
| FRPB | | | | | 0-0 | 34-61-14 | | D41595J | | | PB | | D41595J | 53 | | 001-099 | |
| FRPB | | | | | 0-0 | 34-61-14 | | D41595J | | | PB | | D41595J | 43 | | 115-199 | |
| FRQV | | | | | 0-0 | 34-61-14 | | D41817J | 25 | | | | D41817J | | QV | 115-199 | |
| FRQW | | | | | 0-0 | 34-61-16 | | D41081J | 15 | | | | D41081J | | QW | 115-199 | |
| FRRT | | | | | 0-0 | 34-22-18 | | D43023J | 8 | | | | D43023J | | RT | 115-199 | |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 | | | | | | | | | | | | |
| 0001 | 24 | | GK | | 2-11 | 34-22-26 | | D00083C | 1 | | | | D41328J | 13 | | 001-099 | |
| 0001 | 24 | | GK | | 2-11 | 34-22-26 | | D41328J | 13 | | | | D00083C | 1 | | 115-199 | |
| 0002 | 24 | | GK | | 2-11 | 34-22-26 | | D00083F | 1 | | | | D41328J | 14 | | 001, 003-099 | |
| 0002 | 22 | | GA | | 4-0 | 34-22-26 | | D00083F | 1 | | | | D41347J | 31 | | 002 | |
| 0002 | 24 | | GK | | 2-11 | 34-22-26 | | D41328J | 14 | | | | D00083F | 1 | | 115-199 | |
| 0003 | 22 | | GA | | 3-4 | 34-22-26 | | D00083F | 4 | | | | D42085J | 11 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 52

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 0003 | 22 | | GA | | 3-4 | 34-22-26 | D42085J | | 11 | | D00083F | | 4 | | 115-199 |
| 0004 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | | F08 | | GD01906 | ST.. | 2 | | ALL |
| 0005 | 20 | | GA | | 3-3 | 34-22-26 | D00083C | | 4 | | GD01906 | AC.. | 2 | | ALL |
| 0006 | 20 | | GA | | 3-3 | 34-22-26 | D00083C | | 6 | | GD01906 | ST.. | 2 | | ALL |
| 0007 | 24 | | GK | | 3-4 | 34-22-27 | D00083A | | F12 | | D42085J | | 45 | | 001-009 |
| 0007 | 24 | | GK | | 3-4 | 34-22-27 | D00083A | | F12 | | TB0203Y | A040 | BJ | | 010-099 |
| 0007 | 24 | | GK | | 3-4 | 34-22-27 | D42085J | | 45 | | D00083A | F12 | | | 115-199 |
| 0008 | 22 | | GA | | 3-3 | 34-22-27 | D00083D | | A12 | | GD01906 | ST.. | 2 | | ALL |
| 0009 | 22 | | GA | | 3-7 | 34-22-27 | D00083D | | A11 | | SM00031 | | WI | | ALL |
| 0010 | 22 | | GA | | 3-3 | 34-22-27 | D00083D | | C11 | | GD01906 | ST.. | 2 | | ALL |
| 0011 | 22 | | GA | | 3-3 | 34-22-27 | D00083D | | J11 | | GD01906 | ST.. | 2 | | ALL |
| 0012 | 22 | | GA | | 3-3 | 34-22-27 | D00083A | | G12 | | GD01906 | ST.. | 2 | | ALL |
| 0013 | 24 | | GK | | 3-4 | 34-22-24 | D41077J | | 28 | | SM00001 | | WI | | 001-099 |
| 0013 | 24 | | GK | | 3-3 | 34-22-24 | D41077J | | 28 | | SM00001 | | WI | | 115-199 |
| 0014 | 24 | | GK | | 3-4 | 34-22-24 | D41077J | | 29 | | SM00002 | | WI | | 001-099 |
| 0014 | 24 | | GK | | 3-3 | 34-22-24 | D41077J | | 29 | | SM00002 | | WI | | 115-199 |
| 0015 | 24 | | GK | | 3-4 | 34-22-24 | D41077J | | 30 | | SM00003 | | WI | | 001-099 |
| 0015 | 24 | | GK | | 3-3 | 34-22-24 | D41077J | | 30 | | SM00003 | | WI | | 115-199 |
| 0016 | 24 | | GK | | 3-7 | 34-22-24 | D00083A | | A09 | | SM00001 | | WI | | ALL |
| 0017 | 24 | | GK | | 3-7 | 34-22-24 | D00083D | | B09 | | SM00002 | | WI | | ALL |
| 0018 | 24 | | GK | | 3-7 | 34-22-24 | D00083A | | C09 | | SM00003 | | WI | | ALL |
| 0019 | 24 | | GK | | 2-7 | 34-22-34 | D41603J | | 41 | | SM00001 | | WI | | ALL |
| 0020 | 24 | | GK | | 2-7 | 34-22-34 | D41603J | | 42 | | SM00002 | | WI | | ALL |
| 0021 | 24 | | GK | | 2-7 | 34-22-34 | D41603J | | 43 | | SM00003 | | WI | | ALL |
| 0022 | 24 | | GK | | 3-7 | 34-22-25 | D41079J | | 28 | | SM00004 | | WI | | 001-099 |
| 0022 | 24 | | GK | | 3-5 | 34-22-25 | D41079J | | 28 | | SM00004 | | WI | | 115-199 |
| 0023 | 24 | | GK | | 3-7 | 34-22-25 | D41079J | | 29 | | SM00005 | | WI | | 001-099 |
| 0023 | 24 | | GK | | 3-5 | 34-22-25 | D41079J | | 29 | | SM00005 | | WI | | 115-199 |
| 0024 | 24 | | GK | | 3-7 | 34-22-25 | D41079J | | 30 | | SM00006 | | WI | | 001-099 |
| 0024 | 24 | | GK | | 3-5 | 34-22-25 | D41079J | | 30 | | SM00006 | | WI | | 115-199 |
| 0025 | 24 | | GK | | 3-7 | 34-22-25 | D00083A | | F09 | | SM00004 | | WI | | ALL |
| 0026 | 24 | | GK | | 3-7 | 34-22-25 | D00083A | | G09 | | SM00005 | | WI | | ALL |
| 0027 | 24 | | GK | | 3-7 | 34-22-25 | D00083A | | H09 | | SM00006 | | WI | | ALL |
| 0028 | 24 | | GK | | 2-7 | 34-22-34 | D41603J | | 44 | | SM00004 | | WI | | ALL |
| 0029 | 24 | | GK | | 2-7 | 34-22-34 | D41603J | | 45 | | SM00005 | | WI | | ALL |
| 0030 | 24 | | GK | | 2-7 | 34-22-34 | D41603J | | 46 | | SM00006 | | WI | | ALL |
| 0031 | 24 | | GK | | 3-6 | 34-22-27 | D42085J | | 42 | | SM00007 | | WI | | ALL |
| 0032 | 24 | | GK | | 3-6 | 34-22-27 | D42085J | | 43 | | SM00008 | | WI | | ALL |
| 0033 | 24 | | GK | | 3-7 | 34-22-27 | D00083D | | J12 | | SM00007 | | WI | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 53

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-----------------------------|----------|---------|------|------|--------|---------|-------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 0034 | 24 | | GK | | 3-7 | 34-22-27 | D00083D | | K12 | | SM00008 | | WI | | ALL | |
| 0035 | 24 | | GK | | 1-11 | 34-22-37 | D41679J | | 7 | | SM00007 | | WI | | 001-099 | |
| 0035 | 24 | | GK | | 2-2 | 34-22-37 | D41679J | | 7 | | SM00007 | | WI | | 115-199 | |
| 0036 | 24 | | GK | | 1-11 | 34-22-37 | D41679J | | 9 | | SM00008 | | WI | | 001-099 | |
| 0036 | 24 | | GK | | 2-2 | 34-22-37 | D41679J | | 9 | | SM00008 | | WI | | 115-199 | |
| 0037 | 24 | | GK | | 3-6 | 34-22-27 | D42085J | | 44 | | SM00009 | | WI | | ALL | |
| 0038 | 24 | | GK | | 3-6 | 34-22-27 | D42085J | | 46 | | SM00010 | | WI | | ALL | |
| 0039 | 24 | | GK | | 3-7 | 34-22-27 | D00083D | | G11 | | SM00009 | | WI | | ALL | |
| 0040 | 24 | | GK | | 3-7 | 34-22-27 | D00083D | | E11 | | SM00010 | | WI | | ALL | |
| 0041 | 24 | | GK | | 1-11 | 34-22-37 | D41679J | | 10 | | SM00009 | | WI | | 001-099 | |
| 0041 | 24 | | GK | | 2-2 | 34-22-37 | D41679J | | 10 | | SM00009 | | WI | | 115-199 | |
| 0042 | 24 | | GK | | 1-11 | 34-22-37 | D41679J | | 8 | | SM00010 | | WI | | 001-099 | |
| 0042 | 24 | | GK | | 2-2 | 34-22-37 | D41679J | | 8 | | SM00010 | | WI | | 115-199 | |
| 0043 | 24 | | GK | | 3-4 | 34-61-11 | D00177A | | J13 | | D41565J | 7 | | | 001-099 | |
| 0043 | 24 | | GK | | 3-5 | 34-61-11 | D41565J | | 7 | | D00177A | J13 | | | 115-199 | |
| 0044 | 24 | | GK | | 2-7 | 34-61-13 | D41603J | | 4 | | SM00011 | | WI | | ALL | |
| 0045 | 24 | | GK | | 2-11 | 34-61-23 | D00177A | | K11 | | SM00011 | | WI | | ALL | |
| 0046 | 22 | | GA | | 2-5 | 34-12-21 | D42085J | | 23 | | GD01903 | AC.. | 2 | | ALL | |
| 0047 | 24 | | GK | | 2-7 | 34-61-13 | D41603J | | 11 | | SM00012 | | WI | | ALL | |
| 0048 | 22 | | GA | | 2-6 | 30-32-11 | D41347J | | 12 | | D42143J | 7 | | | 001-099 | |
| 0048 | 22 | | GA | | 2-5 | 30-32-11 | D41347J | | 12 | | D42143J | 7 | | | 115-199 | |
| 0049 | 22 | | GA | | 2-11 | 34-61-23 | D00177B | | A15 | | SM00012 | | WI | | ALL | |
| 004CO | | | | HO | 0-0 | 34-31-21 | D00205C | | = C1 | | D42123J | = C1 | | | 001-099 | |
| 004CO | | | | CM | 0-0 | 34-31-21 | D42123J | | = C1 | | D02941C | = C12 | | | 115-199 | |
| 004CX | | 94 | | HO | 1-2 | 34-31-21 | D00205C | | 1 | | D42123J | = A1 | | | 001-099 | |
| 004CX | | 94 | | CM | 1-2 | 34-31-21 | D42123J | | = A1 | | D02941C | 12 | | | 115-199 | |
| 0050 | 22 | | GA | | 3-4 | 34-61-23 | D00177B | | A13 | | D41565J | 21 | | | 001-099 | |
| 0050 | 22 | | GA | | 3-5 | 34-61-23 | D41565J | | 21 | | D00177B | A13 | | | 115-199 | |
| 0051 | 24 | | GK | | 3-4 | 34-61-23 | D00177A | | K09 | | D41565J | 22 | | | 001-099 | |
| 0051 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | | 22 | | D00177A | K09 | | | 115-199 | |
| 0052 | 24 | | GK | | 3-4 | 34-61-23 | D00177B | | B14 | | D41565J | 26 | | | 001-099 | |
| 0052 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | | 26 | | D00177B | B14 | | | 115-199 | |
| 0053 | 24 | | GK | | 3-4 | 34-61-23 | D00177B | | C14 | | D41565J | 27 | | | 001-099 | |
| 0053 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | | 27 | | D00177B | C14 | | | 115-199 | |
| 0054 | 24 | | GK | | 3-4 | 34-61-23 | D00177B | | F14 | | D41565J | 28 | | | 001-099 | |
| 0054 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | | 28 | | D00177B | F14 | | | 115-199 | |
| 0055 | 24 | | GK | | 3-4 | 34-61-23 | D00177B | | G13 | | D41565J | 29 | | | 001-099 | |
| 0055 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | | 29 | | D00177B | G13 | | | 115-199 | |
| 0056 | 24 | | GK | | 3-4 | 34-61-23 | D00177B | | J14 | | D41565J | 30 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 54

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|-------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 0056 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | 30 | | | D00177B | J14 | | | 115-199 |
| 0057 | 24 | | GK | | 3-4 | 34-61-23 | D00177B | J13 | | | D41565J | 31 | | | 001-099 |
| 0057 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | 31 | | | D00177B | J13 | | | 115-199 |
| 0058 | 24 | | GK | | 3-4 | 34-61-23 | D00177B | A14 | | | D41565J | 32 | | | 001-099 |
| 0058 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | 32 | | | D00177B | A14 | | | 115-199 |
| 0059 | 24 | | GK | | 3-4 | 34-61-23 | D00177B | F13 | | | D41565J | 33 | | | 001-099 |
| 0059 | 24 | | GK | | 3-5 | 34-61-23 | D41565J | 33 | | | D00177B | F13 | | | 115-199 |
| 005CO | | | | AC | 0-0 | 34-31-21 | D00205C | = C5 | | | D42127J | = C1 | | | 001-099 |
| 005CO | | | | CN | 0-0 | 34-31-21 | D42127J | = C1 | | | D02941C | = C13 | | | 115-199 |
| 005CX | | 94 | | AC | 1-5 | 34-31-21 | D00205C | 5 | | | D42127J | = A1 | | | 001-099 |
| 005CX | | 94 | | CN | 1-7 | 34-31-21 | D42127J | = A1 | | | D02941C | 13 | | | 115-199 |
| 0063 | 24 | | GK | | 3-0 | 34-61-25 | D00177A | K13 | | | D41603J | 34 | | | 001-099 |
| 0063 | 24 | | GK | | 3-0 | 34-61-25 | D41603J | 34 | | | D00177A | K13 | | | 115-199 |
| 0064 | 24 | | GK | | 3-4 | 34-61-25 | D00177B | K07 | | | D41345J | 17 | | | 001-099 |
| 0064 | 24 | | GK | | 3-6 | 34-61-25 | D41345J | 17 | | | D00177B | K07 | | | 115-199 |
| 0066 | 24 | | GK | | 3-8 | 34-43-12 | D41063J | 10 | | | D41077J | 34 | | | 001, 003-099 |
| 0066 | 24 | | GK | | 3-8 | 34-43-12 | D41063J | REF | VP | | D41077J | 34 | | | 002 |
| 0066 | 24 | | GK | | 3-11 | 34-43-12 | D41063J | 10 | | | D41077J | 42 | | | 115-199 |
| 0069 | 22 | | GA | | 3-0 | 22-13-21 | D00205B | C01 | | | SM00013 | | WI | | 001-099 |
| 0069 | 22 | | GA | | 3-0 | 22-13-21 | D02941B | F15 | | | SM00013 | | WI | | 115-199 |
| 006CO | | | | IW | 0-0 | 34-58-21 | D02941A | = C2 | | | D45019J | = C1 | | | 115-199 |
| 006CX | | | | IW | 4-0 | 34-58-21 | D02941A | 2 | | | D45019J | = A1 | | | 115-199 |
| 0070 | 22 | | GA | | 4-0 | 22-13-21 | D00075B | H03 | | | SM00013 | | WI | | ALL |
| 0071 | 24 | | GK | | 2-3 | 34-31-21 | D42107J | 5 | | | SM00013 | | WI | | 001-099 |
| 0071 | 24 | | GK | | 2-7 | 34-31-21 | D42107J | 5 | | | SM00013 | | WI | | 115-199 |
| 0072 | 24 | | GK | | 2-4 | 34-61-24 | D41345J | 10 | | | SM00039 | | WI | | 001-099 |
| 0072 | 24 | | GK | | 2-5 | 34-61-24 | D41345J | 10 | | | SM00039 | | WI | | 115-199 |
| 0075 | 24 | | GK | | 3-5 | 34-61-23 | D41347J | 36 | | | SM00011 | | WI | | 001-099 |
| 0075 | 24 | | GK | | 3-4 | 34-61-23 | D41347J | 36 | | | SM00011 | | WI | | 115-199 |
| 0076 | 20 | | GA | | 4-9 | 22-11-21 | D00075C | 6 | | | D41328J | 3 | | | 001-099 |
| 0076 | 20 | | GA | | 4-9 | 22-11-21 | D41328J | 3 | | | D00075C | 6 | | | 115-199 |
| 0077 | 20 | | GA | | 5-4 | 22-11-21 | D00075C | 7 | | | GD01902 | ST.. | 2 | | ALL |
| 0078 | 20 | | GA | | 5-4 | 22-11-21 | D00075C | 4 | | | GD01902 | AC.. | 2 | | ALL |
| 0079 | 20 | | GA | | 2-8 | 22-11-22 | D41328J | 6 | | | SM00015 | | WI | | ALL |
| 0080 | 20 | | GA | | 3-0 | 22-11-22 | D00075C | 2 | | | SM00016 | | WI | | ALL |
| 0081 | 20 | | GA | | 2-8 | 22-11-22 | D41328J | 11 | | | SM00016 | | WI | | ALL |
| 0082 | 20 | | GA | | 3-0 | 22-11-22 | D00075C | 5 | | | SM00016 | | WI | | ALL |
| 0083 | 22 | | GA | | 3-0 | 22-11-22 | D00075C | 1 | | | SM00016 | | WI | | ALL |
| 0084 | 22 | | GA | | 4-0 | 22-11-22 | D00075A | H15 | | | SM00017 | | WI | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 55

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 0085 | 22 | | GA | | 6-1 | 22-11-22 | D42085J | | 36 | | D00075B | G11 | | | 115-199 |
| 0086 | 22 | | GA | | 4-0 | 22-11-22 | D00075B | | H15 | | SM00017 | | WI | | ALL |
| 0088 | 22 | | GA | | 3-5 | 34-12-21 | D42085J | | 22 | | TB0203Z | 60 | BJ | | ALL |
| 0089 | 22 | | GA | | 3-1 | 22-11-22 | D00075B | | F15 | | D41703J | 1 | | | 001-099 |
| 0089 | 22 | | GA | | 3-1 | 22-11-22 | D41703J | | 1 | | D00075B | F15 | | | 115-199 |
| 0090 | 22 | | GA | | 0-7 | 22-11-22 | D00075B | | G13 | | D00075B | H14 | | | 115-199 |
| 0091 | 20 | | GA | | 4-10 | 22-11-22 | D41703J | | 6 | | GD01902 | DC.. | 2 | | ALL |
| 0092 | 22 | | GA | | 5-4 | 22-11-22 | D00075A | | A04 | | GD01902 | DC.. | 2 | | ALL |
| 0093 | 22 | | GA | | 5-4 | 22-11-22 | D00075A | | G11 | | GD01902 | DC.. | 2 | | ALL |
| 0094 | 22 | | GA | | 0-7 | 22-11-22 | D00075B | | E04 | | D00075B | A03 | | | 001-008, 115-199 |
| 0095 | 22 | | GA | | 0-7 | 22-11-22 | D00075A | | B13 | | D00075A | B14 | | | 001-008, 115-199 |
| 0095 | 22 | | GA | | 0-7 | 22-11-23 | D00075A | | B13 | | D00075A | B14 | | | 009-099 |
| 0096 | 22 | | GA | | 0-7 | 22-11-22 | D00075A | | A12 | | D00075A | A11 | | | 001-008, 115-199 |
| 0096 | 22 | | GA | | 0-7 | 22-11-23 | D00075A | | A12 | | D00075A | A11 | | | 009-099 |
| 0097 | 22 | | GA | | 3-4 | 22-11-22 | D00075B | | H11 | | D41907J | 16 | | | 001-099 |
| 0097 | 22 | | GA | | 3-8 | 22-11-22 | D41907J | | 16 | | D00075B | H11 | | | 115-199 |
| 0099 | 22 | | GA | | 3-4 | 22-11-22 | D00075B | | C07 | | D41907J | 15 | | | 001-099 |
| 0099 | 22 | | GA | | 3-8 | 22-11-22 | D41907J | | 15 | | D00075B | C07 | | | 115-199 |
| 0100 | 22 | | GA | | 3-4 | 22-11-22 | D00075B | | A06 | | D41907J | 14 | | | 001-099 |
| 0100 | 22 | | GA | | 3-8 | 22-11-22 | D41907J | | 14 | | D00075B | A06 | | | 115-199 |
| 0101 | 22 | | GA | | 3-4 | 22-11-22 | D00075B | | C15 | | D41624J | 21 | | | 001-099 |
| 0101 | 22 | | GA | | 3-7 | 22-11-22 | D41624J | | 21 | | D00075B | C15 | | | 115-199 |
| 0102 | 22 | | GA | | 3-4 | 22-11-22 | D00075A | | C15 | | D41624J | 2 | | | 001-099 |
| 0102 | 22 | | GA | | 3-7 | 22-11-22 | D41624J | | 2 | | D00075A | C15 | | | 115-199 |
| 0103 | 22 | | GA | | 3-3 | 22-11-22 | D00075A | | K15 | | D41693J | 19 | | | 001-099 |
| 0103 | 22 | | GA | | 3-7 | 22-11-22 | D41693J | | 19 | | D00075A | K15 | | | 115-199 |
| 0104 | 22 | | GA | | 3-3 | 22-11-22 | D00075B | | K15 | | D41693J | 14 | | | 001-099 |
| 0104 | 22 | | GA | | 3-7 | 22-11-22 | D41693J | | 14 | | D00075B | K15 | | | 115-199 |
| 0105 | 22 | | GA | | 3-3 | 22-11-22 | D00075B | | A15 | | D41693J | 1 | | | 001-099 |
| 0105 | 22 | | GA | | 3-7 | 22-11-22 | D41693J | | 1 | | D00075B | A15 | | | 115-199 |
| 0106 | 22 | | GA | | 3-3 | 22-11-22 | D00075A | | A15 | | D41693J | 17 | | | 001-099 |
| 0106 | 22 | | GA | | 3-7 | 22-11-22 | D41693J | | 17 | | D00075A | A15 | | | 115-199 |
| 0107 | 22 | | GA | | 3-6 | 22-11-22 | D42085J | | 34 | | SM00015 | | WI | | ALL |
| 0108 | 22 | | GA | | 3-6 | 22-11-22 | D42085J | | 35 | | SM00016 | | WI | | ALL |
| 0109 | 22 | | GA | | 2-6 | 22-11-22 | D42085J | | 37 | | SM00017 | | WI | | ALL |
| 0110 | 22 | | GA | | 6-0 | 22-12-21 | D00075B | | E10 | | D41347J | 8 | | | 001-099 |
| 0110 | 22 | | GA | | 5-5 | 22-12-21 | D41347J | | 8 | | D00075B | E10 | | | 115-199 |
| 0111 | 20 | | GA | | 2-6 | 22-12-21 | D41703J | | 7 | | GD01914 | DC.. | 2 | | ALL |
| 0112 | 22 | | GA | | 3-1 | 22-12-21 | D00075A | | F15 | | D41703J | 8 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 56

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 0112 | 22 | | GA | | 3-1 | 22-12-21 | D41703J | | 8 | | D00075A | F15 | | | 115-199 |
| 0113 | 22 | | GA | | 6-0 | 22-12-21 | D00075B | | D08 | | D41347J | 1 | | | 001-099 |
| 0113 | 22 | | GA | | 5-5 | 22-12-21 | D41347J | | 1 | | D00075B | D08 | | | 115-199 |
| 0114 | 22 | | GA | | 6-0 | 22-12-21 | D00075B | | C09 | | D41347J | 2 | | | 001-099 |
| 0114 | 22 | | GA | | 5-5 | 22-12-21 | D41347J | | 2 | | D00075B | C09 | | | 115-199 |
| 0115 | 22 | | GA | | 6-0 | 22-12-21 | D00075B | | D10 | | D41347J | 3 | | | 001-099 |
| 0115 | 22 | | GA | | 5-5 | 22-12-21 | D41347J | | 3 | | D00075B | D10 | | | 115-199 |
| 0116 | 22 | | GA | | 6-0 | 22-12-21 | D00075B | | D09 | | D41347J | 4 | | | 001-099 |
| 0116 | 22 | | GA | | 5-5 | 22-12-21 | D41347J | | 4 | | D00075B | D09 | | | 115-199 |
| 0117 | 22 | | GA | | 4-0 | 22-22-21 | D00075B | | G09 | | SM00024 | | WI | | ALL |
| 0118 | 22 | | GA | | 4-0 | 22-22-21 | D00075A | | G09 | | SM00024 | | WI | | ALL |
| 0119 | 22 | | GA | | 4-4 | 22-22-21 | D00075A | | F12 | | D41345J | 34 | | | 001-099 |
| 0119 | 22 | | GA | | 4-5 | 22-22-21 | D41345J | | 34 | | D00075A | F12 | | | 115-199 |
| 0120 | 22 | | GA | | 3-1 | 22-14-11 | D41907J | | 18 | | SM00023 | | WI | | 001-099 |
| 0120 | 22 | | GA | | 3-4 | 22-14-11 | D41907J | | 18 | | SM00023 | | WI | | 115-199 |
| 0128 | 22 | | GA | | 2-5 | 22-14-31 | D41347J | | 55 | | SM00023 | | WI | | 001-099 |
| 0128 | 22 | | GA | | 2-4 | 22-14-31 | D41347J | | 55 | | SM00023 | | WI | | 115-199 |
| 0129 | 22 | | GA | | 3-1 | 22-14-31 | D41907J | | 17 | | SM00023 | | WI | | 001-099 |
| 0129 | 22 | | GA | | 3-4 | 22-14-31 | D41907J | | 17 | | SM00023 | | WI | | 115-199 |
| 0134 | 22 | | GA | | 2-6 | 22-14-21 | D42085J | | 5 | | SM00018 | | WI | | ALL |
| 0135 | 22 | | GA | | 4-0 | 22-14-21 | D00075B | | K10 | | SM00018 | | WI | | ALL |
| 0136 | 22 | | GA | | 2-6 | 22-14-21 | D42085J | | 6 | | SM00019 | | WI | | ALL |
| 0137 | 22 | | GA | | 4-0 | 22-14-21 | D00075B | | J11 | | SM00019 | | WI | | ALL |
| 0138 | 22 | | GA | | 3-6 | 22-14-21 | D42085J | | 7 | | SM00015 | | WI | | ALL |
| 0139 | 22 | | GA | | 2-6 | 22-14-21 | D42085J | | 4 | | SM00020 | | WI | | 001-099 |
| 0139 | 22 | | GA | | 3-11 | 22-14-21 | D42085J | | 4 | | TB0203Z | 81 | BJ | | 115-199 |
| 0140 | 22 | | GA | | 4-0 | 22-14-21 | D00075B | | K11 | | SM00020 | | WI | | 001-099 |
| 0140 | 22 | | GA | | 3-7 | 22-14-21 | D00075B | | K11 | | TB0203Z | 81 | BJ | | 115-199 |
| 0141 | 24 | | GK | | 2-10 | 34-22-16 | D00083D | | B12 | | D41603J | 32 | | | 001-099 |
| 0141 | 24 | | GK | | 2-10 | 34-22-16 | D41603J | | 32 | | D00083D | B12 | | | 115-199 |
| 0143 | 22 | | GA | | 4-0 | 22-14-21 | D00075B | | K12 | | SM00014 | | WI | | ALL |
| 0144 | 22 | | GA | | 3-3 | 22-14-21 | D00075B | | J12 | | D41679J | 32 | | | 001-099 |
| 0144 | 22 | | GA | | 3-5 | 22-14-21 | D00075B | | J12 | | D41679J | 32 | | | 115-199 |
| 0149 | 22 | | GA | | 4-0 | 22-14-21 | D00075A | | C13 | | SM00023 | | WI | | ALL |
| 0151 | 22 | | GA | | 2-11 | 22-15-12 | D41679J | | 43 | | SM00025 | | WI | | 001-099 |
| 0151 | 22 | | GA | | 3-2 | 22-15-12 | D41679J | | 43 | | SM00025 | | WI | | 115-199 |
| 0152 | 22 | | GA | | 4-0 | 22-15-12 | D00075A | | G10 | | SM00025 | | WI | | ALL |
| 0153 | 22 | | GA | | 2-11 | 22-15-12 | D41679J | | 42 | | SM00025 | | WI | | 001-099 |
| 0153 | 22 | | GA | | 3-2 | 22-15-12 | D41679J | | 42 | | SM00025 | | WI | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 57

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|----|-------|-------------|-------|------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | | | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | |
| 0155 | 22 | GA | | | 2-4 | 22-22-21 | D41345J | 30 | | | SM00024 | | WI | | 001-099 |
| 0155 | 22 | GA | | | 2-5 | 22-22-21 | D41345J | 30 | | | SM00024 | | WI | | 115-199 |
| 0156 | 22 | GA | | | 2-6 | 32-31-11 | D42085J | 24 | | | D41347J | 50 | | | 001-099 |
| 0156 | 22 | GA | | | 2-5 | 32-31-11 | D42085J | 24 | | | D41347J | 50 | | | 115-199 |
| 0158 | 22 | GA | | | 6-1 | 22-41-13 | D00075B | F09 | | | D42085J | 41 | | | 001-099 |
| 0158 | 22 | GA | | | 6-1 | 22-41-13 | D42085J | 41 | | | D00075B | F09 | | | 115-199 |
| 0159 | 24 | GK | | | 4-3 | 34-12-22 | D00291B | E03 | | | SM00029 | | WI | | ALL |
| 0161 | 22 | GA | | | 3-10 | 34-31-21 | D00205C | 2 | | | D41328J | 2 | | | 001-099 |
| 0161 | 22 | GA | | | 3-10 | 34-31-21 | D41328J | 2 | | | D02941C | 9 | | | 115-199 |
| 0162 | 20 | GA | | | 4-4 | 34-31-21 | D00205C | 3 | | | GD01902 | AC.. | 2 | | 001-099 |
| 0162 | 20 | GA | | | 4-4 | 34-31-21 | D02941C | 7 | | | GD01902 | AC.. | 2 | | 115-199 |
| 0163 | 20 | GA | | | 4-4 | 34-31-21 | D00205C | 4 | | | GD01902 | ST.. | 2 | | 001-099 |
| 0163 | 20 | GA | | | 4-4 | 34-31-21 | D02941C | 8 | | | GD01902 | ST.. | 2 | | 115-199 |
| 0164 | 22 | GA | | | 3-5 | 34-31-21 | D00205B | D15 | | | TB0203Z | 44 | BJ | | 001-099 |
| 0164 | 22 | GA | | | 3-5 | 34-31-21 | D02941B | A04 | | | TB0203Z | 44 | BJ | | 115-199 |
| 0165 | 24 | GK | | | 2-11 | 34-33-21 | D41347J | 32 | | | TB0203Z | 44 | BJ | | 001-099 |
| 0165 | 24 | GK | | | 2-10 | 34-33-21 | D41347J | 32 | | | TB0203Z | 44 | BJ | | 115-199 |
| 0166 | 24 | GK | | | 3-11 | 34-31-21 | D00083A | E12 | | | D42107J | 11 | | | 001-099 |
| 0166 | 24 | GK | | | 4-3 | 34-31-21 | D42107J | 11 | | | D00083A | E12 | | | 115-199 |
| 0167 | 24 | GK | | | 2-8 | 34-51-21 | D43007J | 8 | | | TB0203Z | 44 | BJ | | 001-099 |
| 0167 | 24 | GK | | | 3-0 | 34-51-21 | D41829J | 11 | | | TB0203Z | 44 | BJ | | 115-199 |
| 0168 | 24 | GK | | | 0-7 | 34-31-21 | D00205B | B03 | | | D00205B | C03 | | | 001-099 |
| 0169 | 24 | GK | | | 0-7 | 34-31-21 | D00205B | B05 | | | D00205B | C05 | | | 001-099 |
| 0170 | 22 | GA | | | 2-6 | 30-32-11 | D41347J | 13 | | | D42143J | 6 | | | 001-099 |
| 0170 | 22 | GA | | | 2-5 | 30-32-11 | D41347J | 13 | | | D42143J | 6 | | | 115-199 |
| 0171 | 22 | GA | | | 0-9 | 34-12-22 | D00291B | F15 | | | SM00027 | | WI | | ALL |
| 0172 | 22 | GA | | | 0-9 | 34-12-22 | D00291B | F05 | | | SM00027 | | WI | | ALL |
| 0173 | 22 | GA | | | 0-9 | 34-12-22 | D00291B | G15 | | | SM00027 | | WI | | ALL |
| 0174 | 24 | GK | | | 4-3 | 34-12-22 | D00291B | F11 | | | SM00028 | | WI | | ALL |
| 0175 | 24 | GK | | | 3-5 | 34-12-22 | D41347J | 16 | | | SM00028 | | WI | | 001-099 |
| 0175 | 24 | GK | | | 3-4 | 34-12-22 | D41347J | 16 | | | SM00028 | | WI | | 115-199 |
| 0176 | 24 | GK | | | 3-3 | 34-12-22 | D00291B | F02 | | | D41347J | 14 | | | 001-099 |
| 0176 | 24 | GK | | | 3-2 | 34-12-22 | D41347J | 14 | | | D00291B | F02 | | | 115-199 |
| 0177 | 24 | GK | | | 3-3 | 34-12-22 | D00291B | F10 | | | D41347J | 15 | | | 001-099 |
| 0177 | 24 | GK | | | 3-2 | 34-12-22 | D41347J | 15 | | | D00291B | F10 | | | 115-199 |
| 0179 | 24 | GK | | | 3-3 | 34-12-22 | D00291B | F09 | | | D41347J | 17 | | | 001-099 |
| 0179 | 24 | GK | | | 3-2 | 34-12-22 | D00291B | F09 | | | D41347J | 17 | | | 115-199 |
| 0181 | 22 | GA | | | 3-2 | 34-12-22 | D00291B | D07 | | | GD01903 | DC.. | 2 | | 001-010 |
| 0181 | 22 | GA | | | 3-4 | 34-12-22 | D00291B | D07 | | | TB0203Z | 36 | BJ | | 011-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 58

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | |
| 0182 | 22 | | GA | | 0-7 | 34-12-22 | D00291B | | D14 | | D00291B | | E14 | | ALL |
| 0183 | 22 | | GA | | 3-2 | 34-12-22 | D00291B | | J06 | | GD01903 | | DC.. | 2 | ALL |
| 0184 | 22 | | GA | | 3-1 | 34-12-22 | D00291B | | E10 | | GD01902 | | DC.. | 2 | 001-099 |
| 0184 | 24 | | GK | | 3-1 | 34-12-22 | D00291B | | E10 | | GD01902 | | ST.. | 2 | 115-199 |
| 0185 | 24 | | GK | | 3-5 | 34-12-22 | D41821J | | 7 | | SM00028 | | WI | | ALL |
| 0186 | 24 | | GK | | 2-8 | 34-12-21 | D41328J | | 1 | | SM00030 | | WI | | ALL |
| 0187 | 24 | | GK | | 3-5 | 34-12-21 | D41347J | | 39 | | SM00030 | | WI | | 001-099 |
| 0187 | 24 | | GK | | 3-4 | 34-12-21 | D41347J | | 39 | | SM00030 | | WI | | 115-199 |
| 0188 | 24 | | GK | | 2-10 | 34-12-21 | D41347J | | 37 | | D41328J | | 12 | | 001-099 |
| 0188 | 24 | | GK | | 2-9 | 34-12-21 | D41347J | | 37 | | D41328J | | 12 | | 115-199 |
| 0189 | 24 | | GK | | 3-11 | 34-12-21 | D41328J | | 9 | | TB0203Z | | 116 | BJ | 001-099 |
| 0189 | 24 | | GK | | 4-0 | 34-12-21 | D41328J | | 9 | | TB0203Z | | 116 | BJ | 115-199 |
| 0190 | 22 | | GA | | 3-2 | 34-12-21 | D00291C | | 6 | | GD01903 | | AC.. | 2 | 001-010, 115-199 |
| 0190 | 22 | | GA | | 3-2 | 34-12-21 | D00291C | | 6 | | GD01903 | | AC.. | 2 | *1 011-099 |
| 0191 | 22 | | GA | | 6-0 | 34-12-21 | D00291C | | 5 | | TB0203Z | | 116 | BJ | ALL |
| 0192 | 16 | | GA | | 3-2 | 34-12-21 | D00291C | | 8 | | GD01903 | | DC.. | 2 | ALL |
| 0193 | 24 | | GK | | 2-7 | 34-12-21 | D41328J | | 8 | | TB0203Z | | 60 | BJ | ALL |
| 0194 | 22 | | GA | | 3-1 | 34-61-23 | D00177B | | B13 | | GD01909 | | ST.. | 2 | 115-199 |
| 0195 | 22 | | GA | | 4-11 | 34-12-21 | D41347J | | 38 | | GD01914 | | AC.. | 2 | 001-099 |
| 0195 | 22 | | GA | | 4-10 | 34-12-21 | D41347J | | 38 | | GD01914 | | AC.. | 2 | 115-199 |
| 0196 | 22 | | GA | | 3-2 | 34-12-21 | D00291C | | 9 | | GD01903 | | AC.. | 2 | 001-010, 115-199 |
| 0196 | 22 | | GA | | 3-2 | 34-12-21 | D00291C | | 9 | | GD01903 | | AC.. | 2 | *1 011-099 |
| 0197 | 22 | | GA | | 4-2 | 34-12-21 | D00291C | | 4 | | TB0203Z | | 60 | BJ | ALL |
| 0198 | 22 | | GA | | 3-3 | 22-14-21 | D00075B | | G12 | | D41679J | | 34 | | 001-099 |
| 0198 | 22 | | GA | | 3-5 | 22-14-21 | D41679J | | 34 | | D00075B | | G12 | | 115-199 |
| 0199 | 22 | | GA | | 3-3 | 22-14-21 | D00075B | | K02 | | D41679J | | 38 | | 001-099 |
| 0199 | 22 | | GA | | 3-5 | 22-14-21 | D41679J | | 38 | | D00075B | | K02 | | 115-199 |
| 0200 | 22 | | GA | | 3-2 | 34-61-21 | D00177C | | 1 | | D41328J | | 5 | | 001-099 |
| 0200 | 22 | | GA | | 3-2 | 34-61-21 | D41328J | | 5 | | D00177C | | 1 | | 115-199 |
| 0201 | 22 | | GA | | 6-0 | 34-12-21 | D00291C | | 10 | | TB0203Z | | 116 | BJ | ALL |
| 0202 | 20 | | GA | | 3-1 | 34-61-21 | D00177C | | 7 | | GD01909 | | AC.. | 2 | ALL |
| 0203 | 20 | | GA | | 3-1 | 34-61-21 | D00177C | | 8 | | GD01909 | | DC.. | 2 | ALL |
| 0204 | 24 | | GK | | 2-5 | 34-61-21 | D41083J | | 11 | | SM00038 | | WI | | 001-099 |
| 0204 | 24 | | GK | | 2-4 | 34-61-21 | D41083J | | 11 | | SM00038 | | WI | | 115-199 |
| 0205 | 24 | | GK | | 2-11 | 34-61-21 | D00177B | | F06 | | SM00038 | | WI | | ALL |
| 0206 | 24 | | GK | | 2-7 | 34-61-21 | D41603J | | 21 | | SM00038 | | WI | | ALL |
| 0207 | 22 | | GA | | 3-1 | 34-61-24 | D00177B | | K05 | | GD01909 | | DC.. | 2 | ALL |
| 0208 | 22 | | GA | | 3-1 | 34-61-24 | D00177B | | K03 | | GD01909 | | DC.. | 2 | ALL |
| 0209 | 22 | | GA | | 3-5 | 34-61-24 | D00177B | | D11 | | GD01911 | | DC.. | 2 | 001-010, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 59

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|------------------------------------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | |
| 0209 | 22 | GA | | | 2-10 | 34-61-24 | D00177B | D11 | | | TB0203Z | 38 | BJ | | 011-099 |
| 0210 | 22 | GA | | | 3-5 | 34-61-24 | D00177B | E11 | | | GD01911 | DC.. | 2 | | 001-010, 115-199 |
| 0210 | 22 | GA | | | 2-10 | 34-61-24 | D00177B | E11 | | | TB0203Z | 38 | BJ | | 011-099 |
| 0211 | 22 | GA | | | 3-5 | 34-61-24 | D00177B | F11 | | | GD01911 | DC.. | # | | 001-010, 115-199 |
| 0211 | 22 | GA | | | 2-10 | 34-61-24 | D00177B | F11 | | | TB0203Z | 37 | BJ | | 011-099 |
| 0212 | 22 | GA | | | 3-5 | 34-61-24 | D00177A | K07 | | | GD01911 | DC.. | 2 | | ALL |
| 0213 | 22 | GA | | | 4-9 | 34-12-21 | D42143J | 1 | | | TB0203Z | 116 | BJ | | ALL |
| 0214 | 22 | GA | | | 2-4 | 34-12-21 | D42143J | 2 | | | GD01902 | AC.. | 2 | | ALL |
| 0215 | 22 | GA | | | 2-4 | 34-12-21 | D42143J | 8 | | | GD01902 | AC.. | 2 | | ALL |
| 0217 | 20 | GA | | | 2-6 | 30-33-11 | D42133J | 6 | | | D41347J | 29 | | | 001-099 |
| 0217 | 20 | GA | | | 2-5 | 30-33-11 | D42133J | 6 | | | D41347J | 29 | | | 115-199 |
| 0218 | 20 | GA | | | 2-6 | 30-33-11 | D42133J | 1 | | | D41347J | 28 | | | 001-099 |
| 0218 | 20 | GA | | | 2-5 | 30-33-11 | D41347J | 28 | | | D42133J | 1 | | | 115-199 |
| 0219 | 22 | GA | | | 2-10 | 27-62-11 | D41703J | 2 | | | D41624J | 13 | | | 001-099 |
| 0219 | 20 | GA | | | 3-0 | 27-62-11 | D41703J | 2 | | | D41624J | 13 | | | 115-199 |
| 0220 | 22 | GA | | | 2-10 | 27-62-11 | D41703J | 3 | | | D41624J | 14 | | | 001-099 |
| 0220 | 20 | GA | | | 3-0 | 27-62-11 | D41703J | 3 | | | D41624J | 14 | | | 115-199 |
| 0221 | 22 | GA | | | 4-9 | 34-12-21 | D42143J | 9 | | | TB0203Z | 116 | BJ | | ALL |
| 0222 | 22 | GA | | | 3-9 | 34-12-21 | D42035J | 21 | | | TB0203Z | 60 | BJ | | 115-199 |
| 0223 | 22 | GA | | | 5-1 | 34-12-21 | D42035J | 22 | | | GD01903 | AC.. | 2 | | 115-199 |
| 0224 | 22 | GA | | | 3-9 | 34-12-21 | D42035J | 27 | | | TB0203Z | 60 | BJ | | ALL |
| 0225 | 22 | GA | | | 5-1 | 34-12-21 | D42035J | 28 | | | GD01903 | AC.. | 2 | | ALL |
| 0226 | 24 | GK | | | 4-2 | 34-61-23 | D00177B | E14 | | | D41743J | 10 | | | 001-099 |
| 0226 | 24 | GK | | | 3-11 | 34-61-23 | D41743J | 10 | | | D00177B | E14 | | | 115-199 |
| 0227 | 24 | GK | | | 4-2 | 34-61-23 | D00177B | D14 | | | D41743J | 11 | | | 001-099 |
| 0227 | 24 | GK | | | 3-11 | 34-61-23 | D41743J | 11 | | | D00177B | D14 | | | 115-199 |
| 0228 | 24 | GK | | | 4-2 | 34-61-23 | D00177B | H13 | | | D41743J | 12 | | | 001-099 |
| 0228 | 24 | GK | | | 3-11 | 34-61-23 | D41743J | 12 | | | D00177B | H13 | | | 115-199 |
| 0229 | 24 | GK | | | 2-4 | 34-61-24 | D00177A | K01 | | | SM00039 | | WI | | ALL |
| 0230 | 24 | GK | | | 2-4 | 34-61-24 | D00177A | F09 | | | SM00039 | | WI | | ALL |
| 0231 | 24 | GK | | | 4-2 | 34-61-23 | D00177B | H14 | | | D41743J | 13 | | | 001-099 |
| 0231 | 24 | GK | | | 3-11 | 34-61-23 | D41743J | 13 | | | D00177B | H14 | | | 115-199 |
| 0232 | 24 | GK | | | 3-7 | 34-22-24 | D00083D | A09 | | | SM00001 | | WI | | ALL |
| 0233 | 24 | GK | | | 3-7 | 34-22-24 | D00083A | B09 | | | SM00002 | | WI | | ALL |
| 0234 | 24 | GK | | | 3-7 | 34-22-24 | D00083D | C09 | | | SM00003 | | WI | | ALL |
| 0235 | 24 | GK | | | 3-7 | 34-22-25 | D00083D | F09 | | | SM00004 | | WI | | ALL |
| 0236 | 24 | GK | | | 3-7 | 34-22-25 | D00083D | G09 | | | SM00005 | | WI | | ALL |
| 0237 | 24 | GK | | | 3-7 | 34-22-25 | D00083D | H09 | | | SM00006 | | WI | | ALL |
| 0238 | 20 | GA | | | 1-6 | 34-22-28 | D41565J | | | AA | GD01908 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 60

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-----------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|--------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | | |
| 0239 | 20 | | GA | | 1-6 | 34-22-29 | D41345J | | | | AB | GD01909 | ST.. | 2 | | ALL | |
| 0240 | 20 | | GA | | 1-6 | 34-61-11 | D41565J | | | | AC | GD01908 | ST.. | 2 | | ALL | |
| 0241 | 20 | | GA | | 1-6 | 34-61-11 | D41565J | | | | AD | GD01908 | ST.. | 2 | | ALL | |
| 0242 | 20 | | GA | | 1-6 | 34-61-11 | D41565J | | | | AE | GD01908 | ST.. | 2 | | ALL | |
| 0243 | 20 | | GA | | 1-6 | 34-61-22 | D41603J | | | | AF | GD01904 | ST.. | 2 | | ALL | |
| 0245 | 20 | | GA | | 1-6 | 34-61-24 | D41345J | | | | AH | GD01909 | ST.. | 2 | | ALL | |
| 0252 | 20 | | GA | | 1-6 | 22-12-21 | D41347J | | | | AO | GD01903 | ST.. | 2 | | ALL | |
| 0253 | 20 | | GA | | 1-6 | 22-41-12 | D41095J | | | | AP | GD01915 | ST.. | 2 | | ALL | |
| 0254 | 20 | | GA | | 1-6 | 34-61-21 | D41083J | | | | AQ | GD01907 | ST.. | 2 | | ALL | |
| 0255 | 20 | | GA | | 1-6 | 34-61-21 | D41603J | | | | AR | GD01904 | ST.. | 2 | | ALL | |
| 0256 | 20 | | GA | | 1-6 | 34-61-23 | D41565J | | | | AS | GD01908 | ST.. | 2 | | ALL | |
| 0257 | 20 | | GA | | 1-6 | 34-61-23 | D41565J | | | | AT | GD01908 | ST.. | 2 | | ALL | |
| 0258 | 20 | | GA | | 1-6 | 34-61-23 | D41565J | | | | AU | GD01908 | ST.. | 2 | | ALL | |
| 0259 | 20 | | GA | | 1-6 | 34-61-23 | D41565J | | | | AV | GD01908 | ST.. | 2 | | ALL | |
| 0260 | 20 | | GA | | 1-6 | 22-41-11 | D41345J | | | | AW | GD01909 | ST.. | 2 | | ALL | |
| 0261 | 20 | | GA | | 1-6 | 34-22-28 | D41881J | | | | AX | GD01912 | ST.. | 2 | | ALL | |
| 0262 | 24 | | GK | | 2-9 | 34-55-21 | D41345J | | 51 | | | TB0203Z | 44 | BJ | | 001-099 | |
| 0262 | 24 | | GK | | 2-10 | 34-55-21 | D41345J | | 51 | | | TB0203Z | 44 | BJ | | 115-199 | |
| 0263 | 24 | | GK | | 2-9 | 34-55-21 | D41345J | | 52 | | | TB0203Z | 44 | BJ | | 001-099 | |
| 0263 | 24 | | GK | | 2-10 | 34-55-21 | D41345J | | 52 | | | TB0203Z | 44 | BJ | | 115-199 | |
| 0264 | 22 | | GA | | 3-4 | 34-51-21 | D42087J | | 7 | | | SM00012 | | WI | | ALL | |
| 0265 | 22 | | GA | | 2-1 | 27-31-11 | D41431J | | 2 | | | D41693J | 33 | | | 001-099 | |
| 0265 | 22 | | GA | | 2-5 | 27-31-11 | D41431J | | 19 | | | D41693J | 33 | | | 115-199 | |
| 0266 | 22 | | GA | | 2-1 | 34-51-21 | D43007J | | 1 | | | SM00012 | | WI | | 001-099 | |
| 0266 | 22 | | GA | | 2-6 | 34-51-21 | D41829J | | 7 | | | SM00012 | | WI | | 115-199 | |
| 0270 | 20 | | GA | | 1-6 | 22-13-21 | D41881J | | | | AY | GD01912 | ST.. | 2 | | 001-099 | |
| 0271 | 20 | | GA | | 1-6 | 22-15-11 | D41393J | | | | AZ | GD01914 | ST.. | 2 | | ALL | |
| 0272 | 20 | | GA | | 1-6 | 22-15-11 | D41347J | | | | BA | GD01903 | ST.. | 2 | | ALL | |
| 0273 | 20 | | GA | | 1-6 | 22-15-11 | D41679J | | | | BB | GD01915 | ST.. | 2 | | ALL | |
| 0274 | 20 | | GA | | 1-6 | 22-15-11 | D41743J | | | | BC | GD01915 | ST.. | 2 | | ALL | |
| 0275 | 20 | | GA | | 1-6 | 31-25-11 | D42085J | | | | BD | GD01903 | ST.. | 2 | | ALL | |
| 0276 | 16 | | GA | | 3-2 | 34-12-21 | D00291C | | 7 | | | GD01903 | AC.. | 2 | | ALL | |
| 0277 | 22 | | GA | | 4-3 | 34-12-21 | D00291C | | 1 | | | SM00030 | | WI | | ALL | |
| 0279 | 22 | | GA | | 0-7 | 22-11-22 | D00075B | | C08 | | | D00075B | E08 | | | 115-199 | |
| 0283 | 20 | | GA | | 2-8 | 34-25-11 | D41881J | | | | ID | GD01913 | ST.. | 2 | | 001, 003-009 | |
| 0283 | 20 | | GA | | 1-6 | 34-25-11 | D41881J | | | | BE | GD01913 | ST.. | 2 | | 115-199 | |
| 0284 | 20 | | GA | | 1-6 | 31-31-22 | D41881J | | | | BF | GD01912 | ST.. | 2 | | 115-199 | |
| 0285 | 24 | | GK | | 0-7 | 34-12-22 | TB0203Z | | 114 | BJ | | TB0203Z | 112 | BJ | | ALL | |
| 0286 | 24 | | GK | | 0-7 | 34-12-22 | TB0203Z | | 113 | BJ | | TB0203Z | 111 | BJ | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 61

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | |
| 0288 | 22 | GA | | | 6-2 | 34-12-21 | D00291C | 11 | | | GD01915 | AC.. | 2 | | ALL |
| 0296 | 22 | GA | | | 3-1 | 34-12-22 | D00291B | E07 | | | GD01902 | DC.. | 2 | | 009 |
| 0296 | 24 | GK | | | 3-4 | 34-12-22 | D00291B | E07 | | | TB0203X | A031 | BJ | | 011-099 |
| 0296 | 22 | GA | | | 3-2 | 34-12-22 | D00291B | E07 | | | GD01903 | DC.. | # | | 115-199 |
| 0297 | 22 | GA | | | 0-7 | 22-11-22 | D00075B | K13 | | | D00075B | K14 | | | 001-008 |
| 0301 | 22 | GA | | | 3-2 | 22-15-12 | D41881J | 31 | | | SM00042 | | WI | | 001-099 |
| 0301 | 22 | GA | | | 2-10 | 22-15-12 | D41881J | 53 | | | SM00042 | | WI | | 115-199 |
| 0302 | 22 | GA | | | 4-0 | 22-15-12 | D00075A | F09 | | | SM00042 | | WI | | ALL |
| 0303 | 22 | GA | | | 3-2 | 22-15-12 | D41881J | 19 | | | SM00042 | | WI | | 001-099 |
| 0303 | 22 | GA | | | 2-10 | 22-15-12 | D41881J | 54 | | | SM00042 | | WI | | 115-199 |
| 0304 | 22 | GA | | | 2-6 | 32-42-11 | D41347J | 52 | | | D42085J | 2 | | | 001-099 |
| 0304 | 22 | GA | | | 2-5 | 32-42-11 | D41347J | 52 | | | D42085J | 2 | | | 115-199 |
| 0305 | 22 | GA | | | 2-10 | 34-22-26 | D00083B | D10 | | | GD01904 | ST.. | # | | ALL |
| 0307 | 22 | GA | | | 0-9 | 34-12-22 | D00291B | D02 | | | SM00027 | | WI | | 001-099 |
| 0307 | 22 | GA | | | 3-2 | 34-12-22 | D00291B | D02 | | | GD01903 | DC.. | 2 | | 115-199 |
| 0308 | 22 | GA | | | 0-9 | 34-12-22 | D00291B | G03 | | | SM00027 | | WI | | 001-099 |
| 0308 | 22 | GA | | | 3-2 | 34-12-22 | D00291B | G03 | | | GD01903 | DC.. | 2 | | 115-199 |
| 0309 | 22 | GA | | | 3-4 | 34-12-22 | D00291B | D06 | | | TB0203X | C033 | BJ | | 011-099 |
| 0309 | 22 | GA | | | 3-2 | 34-12-22 | D42087J | 8 | | | D00291B | D06 | | | 115-199 |
| 0310 | 22 | GA | | | 3-2 | 34-12-22 | D42087J | 9 | | | D00291B | D07 | | | 115-199 |
| 0312 | 22 | GA | | | 2-6 | 34-12-22 | TB0203Z | 105 | BJ | | TB0203Z | 111 | BJ | | ALL |
| 0314 | 22 | GA | | | 5-2 | 22-14-11 | D42035J | 7 | | | D41347J | 53 | | | 001-099 |
| 0314 | 22 | GA | | | 5-1 | 22-14-11 | D42035J | 7 | | | D41347J | 53 | | | 115-199 |
| 0315 | 22 | GA | | | 5-2 | 22-14-11 | D42035J | 8 | | | D41347J | 54 | | | 001-099 |
| 0315 | 22 | GA | | | 5-1 | 22-14-11 | D42035J | 8 | | | D41347J | 54 | | | 115-199 |
| 0316 | 22 | GA | | | 2-10 | 34-22-26 | D00083B | E10 | | | GD01904 | ST.. | 2 | | ALL |
| 0317 | 22 | GA | | | 2-10 | 34-22-26 | D00083B | F09 | | | GD01904 | ST.. | 2 | | 001-099 |
| 0317 | 22 | GA | | | 2-10 | 34-22-26 | D00083B | F09 | | | GD01904 | ST.. | # | | 115-199 |
| 0318 | 22 | GA | | | 2-10 | 34-22-26 | D00083B | E08 | | | GD01904 | ST.. | 2 | | ALL |
| 0319 | 22 | GA | | | 2-10 | 34-22-26 | D00083B | D11 | | | GD01904 | ST.. | 2 | | ALL |
| 0320 | 24 | GK | | | 2-1 | 31-51-21 | D41907J | 22 | | | SM00043 | | WI | | 001-099 |
| 0320 | 24 | GK | | | 2-4 | 31-51-21 | D41907J | 22 | | | SM00043 | | WI | | 115-199 |
| 0323 | 22 | GA | | | 2-4 | 34-22-26 | D42087J | 24 | | | SM00035 | | WI | | ALL |
| 0324 | 24 | GK | | | 2-1 | 34-12-22 | D41907J | 10 | | | SM00043 | | WI | | 001-099 |
| 0324 | 24 | GK | | | 2-4 | 34-12-22 | D41907J | 10 | | | SM00043 | | WI | | 115-199 |
| 0325 | 24 | GK | | | 2-8 | 34-12-22 | D42035J | 4 | | | SM00043 | | WI | | 001-099 |
| 0325 | 24 | GK | | | 2-8 | 34-12-22 | D42035J | 34 | | | SM00043 | | WI | | 115-199 |
| 0327 | 22 | GA | | | 3-4 | 34-22-26 | D00083B | E09 | | | GD01905 | ST.. | # | | 001-099 |
| 0327 | 22 | GA | | | 3-4 | 34-22-26 | D00083B | E09 | | | GD01905 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 62

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|---------------------------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | | |
| 0328 | 22 | | PA | | 0-12 | 22-11-22 | D00075B | D03 | | | D00075B | K04 | | | 115-199 | |
| 0330 | 22 | | GA | | 2-6 | 34-12-22 | TB0203Z | 106 | BJ | | TB0203Z | 112 | BJ | | ALL | |
| 0331 | 22 | | GA | | 3-9 | 34-61-23 | D00177B | B13 | | | GD01902 | ST.. | 2 | | | 001-003, 005, 009-010 |
| 0331 | 22 | | GA | | 3-9 | 34-61-23 | D00177B | B13 | | | GD01902 | ST.. | # | | | 004, 006-008 |
| 0331 | 22 | | GA | | 3-0 | 34-61-23 | D00177B | B13 | | | TB0203Z | 50 | BJ | | 011-099 | |
| 0333 | 22 | | GA | | 3-4 | 34-22-26 | D00083B | D07 | | | GD01905 | ST.. | # | | ALL | |
| 0334 | 22 | | GA | | 3-4 | 34-22-26 | D00083B | G09 | | | GD01905 | ST.. | 2 | | 001-099 | |
| 0334 | 22 | | GA | | 3-4 | 34-22-26 | D00083B | G09 | | | GD01905 | ST.. | # | | 115-199 | |
| 0335 | 22 | | GA | | 2-7 | 34-22-26 | D00083B | D08 | | | SM00035 | | WI | | ALL | |
| 0336 | 22 | | GA | | 3-4 | 34-22-26 | D00083B | E11 | | | GD01905 | ST.. | # | | 001-006, 009-099, 115-199 | |
| 0336 | 22 | | GA | | 3-4 | 34-22-26 | D00083B | E11 | | | GD01905 | ST.. | 2 | | 007-008 | |
| 0337 | 22 | | GA | | 3-4 | 34-22-26 | D00083B | F11 | | | GD01905 | ST.. | 2 | | 001, 009 | |
| 0337 | 22 | | GA | | 3-4 | 34-22-26 | D00083B | F11 | | | GD01905 | ST.. | # | | 002-008, 010-099, 115-199 | |
| 0338 | 22 | | GA | | 3-4 | 34-22-26 | D00083B | D09 | | | GD01905 | ST.. | # | | ALL | |
| 0339 | 22 | | GA | | 2-4 | 34-61-24 | D00177A | K04 | | | SM00035 | | WI | | ALL | |
| 0340 | 22 | | GA | | 4-0 | 22-13-21 | D00075B | H02 | | | SM00035 | | WI | | ALL | |
| 0341 | 22 | | GA | | 3-0 | 34-61-24 | D00177B | C11 | | | GD01905 | DC.. | # | | 001-010, 115-199 | |
| 0341 | 22 | | GA | | 2-10 | 34-61-24 | D00177B | C11 | | | TB0203Z | 37 | BJ | | 011-099 | |
| 0342 | 22 | | GA | | 3-0 | 34-61-24 | D00177B | G11 | | | GD01905 | DC.. | 2 | | 001-010, 115-199 | |
| 0342 | 22 | | GA | | 2-10 | 34-61-24 | D00177B | G11 | | | TB0203Z | 38 | BJ | | 011-099 | |
| 0343 | 22 | | GA | | 3-0 | 34-61-24 | D00177B | H11 | | | GD01905 | DC.. | # | | 001-010, 115-199 | |
| 0343 | 22 | | GA | | 2-10 | 34-61-24 | D00177B | H11 | | | TB0203Z | 37 | BJ | | 011-099 | |
| 0344 | 22 | | GA | | 3-0 | 34-61-24 | D00177B | C15 | | | GD01905 | DC.. | # | | 001-010, 115-199 | |
| 0344 | 22 | | GA | | 2-10 | 34-61-24 | D00177B | C15 | | | TB0203Z | 37 | BJ | | 011-099 | |
| 0345 | 24 | | GK | | 3-4 | 34-12-22 | D00291B | F07 | | | TB0203X | B031 | BJ | | 011-099 | |
| 0346 | 22 | | GA | | 3-0 | 34-61-24 | D00177B | D15 | | | GD01905 | DC.. | # | | 001-010, 115-199 | |
| 0346 | 22 | | GA | | 3-8 | 34-61-24 | D00177B | D15 | | | TB0203Z | 1 | BJ | | 011-099 | |
| 0347 | 22 | | GA | | 3-0 | 34-61-24 | D00177B | E15 | | | GD01905 | DC.. | # | | 001-010, 115-199 | |
| 0347 | 22 | | GA | | 3-8 | 34-61-24 | D00177B | E15 | | | TB0203Z | 1 | BJ | | 011-099 | |
| 0348 | 22 | | GA | | 3-0 | 34-61-24 | D00177B | F15 | | | GD01905 | DC.. | # | | 001-010, 115-199 | |
| 0348 | 22 | | GA | | 3-8 | 34-61-24 | D00177B | F15 | | | TB0203Z | 1 | BJ | | 011-099 | |
| 0349 | 22 | | GA | | 3-0 | 34-61-23 | D00177B | D13 | | | TB0203Z | 49 | BJ | | 011-099 | |
| 0350 | 22 | | GA | | 3-0 | 34-61-23 | D00177B | B15 | | | TB0203Z | 49 | BJ | | 011-099 | |
| 0351 | 22 | | GA | | 3-2 | 22-14-11 | D41743J | 5 | | | SM00018 | | WI | | 001-099 | |
| 0352 | 22 | | GA | | 3-1 | 34-61-25 | D41907J | 13 | | | D42035J | 14 | | | 001-099 | |
| 0352 | 22 | | GA | | 3-4 | 34-61-25 | D41907J | 13 | | | D42035J | 14 | | | 115-199 | |
| 0353 | 22 | | GA | | 3-2 | 22-14-11 | D41743J | 6 | | | SM00020 | | WI | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 63

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | | | | | | | | | | | | | | | |
| | | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | |
| 0354 | 24 | GK | | | 3-4 | SPARE | D41907J | 39 | | | D42035J | 35 | | | 115-199 |
| 0355 | 24 | GK | | | 3-4 | SPARE | D41907J | 40 | | | D42035J | 36 | | | 115-199 |
| 0356 | 22 | GA | | | 3-2 | 22-14-11 | D41743J | 8 | | | SM00022 | | WI | | 001-099 |
| 0357 | 22 | GA | | | 3-2 | 22-14-31 | D41393J | 13 | | | SM00019 | | WI | | 001-099 |
| 0358 | 22 | GA | | | 3-5 | 22-14-31 | D41095J | 10 | | | SM00022 | | WI | | 001-099 |
| 0359 | 22 | GA | | | 3-2 | 22-14-31 | D41393J | 15 | | | SM00020 | | WI | | 001-099 |
| 0360 | 22 | GA | | | 3-2 | 22-14-31 | D41393J | 24 | | | SM00014 | | WI | | 001-099 |
| 0361 | 22 | GA | | | 3-2 | 22-14-31 | D41393J | 16 | | | SM00018 | | WI | | 001-099 |
| 0362 | 22 | GA | | | 3-2 | 22-14-21 | D41393J | 11 | | | SM00014 | | WI | | 001-099 |
| 0363 | 22 | GA | | | 4-0 | 22-14-21 | D00075B | K03 | | | SM00022 | | WI | | 001-099 |
| 0364 | 22 | GA | | | 3-1 | 22-14-21 | D00075B | E12 | | | D41095J | 6 | | | 001-099 |
| 0366 | 22 | GA | | | 3-6 | 22-14-21 | D00075A | E12 | | | D41393J | 36 | | | 001-099 |
| 0367 | 22 | GA | | | 3-1 | 22-14-21 | D00075A | F01 | | | D41095J | 5 | | | 001-099 |
| 0368 | 22 | GA | | | 3-6 | 22-15-12 | D00075A | K03 | | | D41393J | 17 | | | 001-099 |
| 0369 | 22 | GA | | | 4-4 | 22-15-12 | D00075A | K01 | | | D41565J | 48 | | | 001-099 |
| 0370 | 22 | GA | | | 3-4 | 22-41-13 | D00075B | F10 | | | D42035J | 23 | | | 001-099 |
| 0371 | 22 | GA | | | 3-2 | 22-14-11 | D41743J | 7 | | | SM00019 | | WI | | 001-099 |
| 0372 | 22 | GA | | | 3-2 | 22-14-11 | D41743J | 14 | | | SM00014 | | WI | | 001-099 |
| 0373 | 22 | GA | | | 3-5 | 22-14-31 | D41095J | 16 | | | SM00022 | | WI | | 001-099 |
| 0374 | 22 | GA | | | 3-1 | 22-41-11 | D00075B | C06 | | | D41095J | 36 | | | 001-099 |
| 0375 | 22 | GA | | | 3-1 | 22-15-12 | D00075A | G01 | | | D41095J | 34 | | | 001-099 |
| 0377 | 22 | GA | | | 3-6 | 22-15-12 | D00075A | E03 | | | D41393J | 40 | | | 001-099 |
| 0378 | 22 | GA | | | 3-1 | 22-41-11 | D00075A | A03 | | | D41095J | 1 | | | 001-099 |
| 0379 | 22 | GA | | | 3-6 | 22-14-21 | D00075A | G12 | | | D41393J | 37 | | | 001-099 |
| 0380 | 22 | GA | | | 3-8 | 22-11-22 | D00075C | 9 | | | D41431J | 1 | | | 001-099 |
| 0381 | 22 | GA | | | 0-7 | 22-11-22 | D00075B | C13 | | | D00075B | F04 | | | 002-008 |
| 0383 | 22 | GA | | | 3-1 | 34-61-23 | D00177B | C13 | | | GD01909 | ST.. | 2 | | 001 |
| 0383 | 22 | GA | | | 3-0 | 34-61-23 | D00177B | C13 | | | TB0203Z | 49 | BJ | | 011-099 |
| 0383 | 22 | GA | | | 3-1 | 34-61-23 | D00177B | C13 | | | GD01909 | ST.. | # | | 115-199 |
| 0384 | 24 | GK | | | 2-10 | 73-21-22 | D41907J | 4 | | | D41703J | 9 | | | 001-099 |
| 0385 | 24 | GK | | | 2-10 | 73-21-22 | D41907J | 5 | | | D41703J | 10 | | | 001-099 |
| 0387 | 22 | GA | | | 3-1 | 34-61-23 | D00177B | C13 | | | GD01909 | ST.. | 2 | | 009 |
| 0398 | 22 | GA | | | 3-8 | 34-61-24 | D00177B | K15 | | | TB0203Z | 1 | BJ | | 011-099 |
| 0401 | 24 | GK | | | 3-2 | 34-45-01 | D41347J | 26 | | | D00083E | G11 | | | 001-099 |
| 0401 | 24 | GK | | | 3-1 | 34-45-01 | D41347J | 26 | | | D00083A | REF | VM | | 115-199 |
| 0402 | 22 | GA | | | 2-3 | 34-45-01 | D41347J | | | LE | GD01902 | ST.. | 2 | | 001-099 |
| 0402 | 22 | GA | | | 2-2 | 34-45-01 | D41347J | | | LL | GD01902 | ST.. | 2 | | 115-199 |
| 0409 | 20 | GA | | | 2-0 | 34-25-12 | D41200J | | | MB | GD01902 | ST.. | 2 | | 002 |
| 0410 | 20 | GA | | | 3-0 | 34-25-12 | D41200J | | | MC | GD01902 | ST.. | 2 | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 64

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 0411 | 22 | | GA | | 5-0 | 34-25-12 | D00083D | F13 | | | D41345J | 44 | | | 002 |
| 0422 | 22 | | GA | | 1-11 | 34-61-24 | TB0203Z | 38 | BJ | | GD01905 | DC.. | 2 | | 011-099 |
| 0424 | 22 | | GA | | 1-11 | 34-61-24 | TB0203Z | 2 | BJ | | GD01902 | DC.. | 2 | | 011-099 |
| 0425 | 24 | | GK | | 3-4 | 34-12-22 | D00291B | E06 | | | TB0203X | C031 | BJ | | 011-099 |
| 0426 | 24 | | GK | | 3-4 | 34-12-22 | D00291B | F06 | | | TB0203X | D031 | BJ | | 011-099 |
| 0427 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | B01 | | | TB0203X | A033 | BJ | | 011-099 |
| 0428 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | C01 | | | TB0203X | B033 | BJ | | 011-099 |
| 0429 | 22 | | GA | | 2-0 | 22-11-22 | D00075B | C13 | | | D00075B | F04 | | | 115-199 |
| 0430 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | D08 | | | TB0203X | A034 | BJ | | 011-099 |
| 0431 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | E05 | | | TB0203X | B034 | BJ | | 011-099 |
| 0432 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | D15 | | | TB0203X | C034 | BJ | | 011-099 |
| 0433 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | E15 | | | TB0203X | D034 | BJ | | 011-099 |
| 0434 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | F08 | | | TB0203X | A032 | BJ | | 011-099 |
| 0435 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | E08 | | | TB0203X | B032 | BJ | | 011-099 |
| 0437 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | J15 | | | TB0203X | C032 | BJ | | 011-099 |
| 0438 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | K15 | | | TB0203X | D032 | BJ | | 011-099 |
| 0439 | 20 | | GA | | 2-7 | 34-12-22 | TB0203Z | 36 | BJ | | GD01905 | DC.. | 2 | | 011-099 |
| 0440 | 20 | | GA | | 2-7 | 34-12-22 | TB0203Z | 35 | BJ | | GD01905 | DC.. | 2 | | 011-099 |
| 0442 | 22 | | GA | | 1-7 | 34-61-23 | TB0203Z | 50 | BJ | | GD01907 | DC.. | 2 | | 011-099 |
| 0458 | 22 | | GA | | 4-0 | 34-12-22 | D00291B | C15 | | | GD01905 | ST.. | 2 | | 001-010, 115-199 |
| 0458 | 22 | | GA | | 3-4 | 34-12-22 | D00291B | C15 | | | TB0203Z | 35 | BJ | | 011-099 |
| 0469 | 20 | | GA | | 3-0 | 34-58-21 | GD01908 | ST.. | 2 | | D41565J | | | BL | 115-199 |
| 0470 | 20 | | GA | | 3-0 | 34-58-21 | GD01911 | ST.. | 2 | | D41881J | | | BN | 115-199 |
| 0471 | 20 | | GA | | 3-0 | 34-58-21 | GD01914 | ST.. | 2 | | D41393J | | | BM | 115-199 |
| 0483 | 24 | | GK | | 1-0 | 34-31-21 | D02941B | B05 | | | D02941B | K04 | | | 115-199 |
| 0491 | 22 | | GA | | 0-7 | 22-11-22 | D00075A | D04 | | | D00075B | A04 | | | 001-008, 115-199 |
| 0494 | 22 | | GA | | 3-2 | 34-22-26 | D00083A | C14 | | | TB0203Y | A039 | BJ | | ALL |
| 0495 | 22 | | GA | | 2-2 | 34-22-26 | D41603J | 53 | | | TB0203Y | A039 | BJ | | ALL |
| 0496 | 22 | | GA | | 3-2 | 34-22-26 | D00083A | K13 | | | TB0203Y | A039 | BJ | | ALL |
| 0497 | 22 | | GA | | 3-4 | 34-22-26 | D00083D | D12 | | | GD01905 | ST.. | 2 | | ALL |
| 0498 | 22 | | GA | | 3-3 | 34-22-27 | D00083D | J13 | | | GD01906 | ST.. | 2 | | ALL |
| 0501 | 22 | | GA | | 2-10 | 34-61-24 | D00177B | H15 | | | TB0203Z | 37 | BJ | | 011-099 |
| 0502 | 22 | | GA | | 2-10 | 34-61-24 | D00177B | J11 | | | TB0203Z | 37 | BJ | | 011-099 |
| 0505 | 24 | | GK | | 3-6 | 34-22-27 | D42085J | 18 | | | SM00031 | | WI | | ALL |
| 0506 | 24 | | GK | | 1-11 | 34-22-37 | D41679J | 33 | | | SM00031 | | WI | | 001-099 |
| 0506 | 24 | | GK | | 2-2 | 34-22-37 | D41679J | 33 | | | SM00031 | | WI | | 115-199 |
| 0507 | 20 | | GA | | 3-8 | 34-22-29 | D41095J | | | LC | GD01909 | ST.. | 2 | | 001-099 |
| 0507 | 20 | | GA | | 3-8 | 34-22-29 | D41095J | | | LC | GD01908 | ST.. | 2 | | 115-199 |
| 0508 | 20 | | GA | | 3-8 | 34-22-29 | D41095J | | | LD | GD01909 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 65

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|------------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | | |
| 0508 | 20 | | GA | | 3-8 | 34-22-29 | D41095J | | | | LD | GD01908 | ST.. | 2 | 115-199 | |
| 0512 | 22 | | GA | | 0-7 | 22-11-22 | D00075B | A12 | | | | D00075B | B15 | | 001-008, 115-199 | |
| 0523 | 22 | | GA | | 3-1 | 34-22-26 | D00083A | B10 | | | | GD01903 | ST.. | # | 003-008 | |
| 0523 | 22 | | GA | | 3-1 | 34-22-26 | D00083A | B10 | | | | GD01903 | ST.. | 2 | 009-099 | |
| 0524 | 22 | | GA | | 3-1 | 34-22-26 | D00083B | G03 | | | | GD01903 | ST.. | # | 003-008 | |
| 0524 | 22 | | GA | | 3-1 | 34-22-26 | D00083B | G03 | | | | GD01903 | ST.. | 2 | 009-099 | |
| 0525 | 22 | | GA | | 3-1 | 34-22-26 | D00083B | H03 | | | | GD01903 | ST.. | # | 003-008 | |
| 0525 | 22 | | GA | | 3-1 | 34-22-26 | D00083B | H03 | | | | GD01903 | ST.. | 2 | 009-099 | |
| 0526 | 22 | | GA | | 3-1 | 34-22-26 | D00083B | J04 | | | | GD01903 | ST.. | # | 003-008 | |
| 0526 | 22 | | GA | | 3-1 | 34-22-26 | D00083B | J04 | | | | GD01903 | ST.. | 2 | 009-099 | |
| 0544 | 22 | | GA | | 3-0 | 34-61-23 | D00177B | K13 | | | | TB0203Z | 49 | BJ | 011-099 | |
| 0557 | 22 | | GA | | 3-1 | 34-22-26 | D00083B | B02 | | | | GD01903 | ST.. | 2 | 009-099 | |
| 0562 | 22 | | GA | | 3-0 | 34-22-26 | D41603J | 33 | | | | D00083A | H14 | | 002 | |
| 0563 | 22 | | GA | | 1-0 | 22-11-22 | D00075B | F11 | | | | D00075B | K09 | | 001 | |
| 0563 | 22 | | GA | | 3-0 | 22-11-22 | D00075B | F11 | | | | D00075B | K09 | | 115-199 | |
| 0564 | 22 | | GA | | 3-0 | 34-22-26 | D41603J | 54 | | | | D00083A | K14 | | 002 | |
| 0569 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | H06 | | | | GD01907 | ST.. | 2 | 010-099 | |
| 0570 | 20 | | GA | | 4-0 | 34-22-28 | GD01911 | ST.. | 2 | | | D22001J | | | 002 | |
| 0571 | 22 | | GA | | 5-0 | 34-22-28 | D00083E | H11 | | | | D41063J | 10 | | 002 | |
| 0575 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | D05 | | | | GD01907 | ST.. | 2 | 001-008, 010-099 | |
| 0575 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | D05 | | | | GD01907 | ST.. | # | 009 | |
| 0576 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | F06 | | | | GD01906 | ST.. | 2 | 001-099 | |
| 0577 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | K04 | | | | GD01906 | ST.. | 2 | 001-099 | |
| 0578 | 20 | | GA | | 3-0 | 34-46-12 | GD01911 | ST.. | 2 | | | D41431J | | | 002 | |
| 0581 | 22 | | GA | | 2-8 | 34-22-28 | D41565J | | | | LE | GD01908 | ST.. | 2 | 115-199 | |
| 0582 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | D12 | | | | GD01906 | ST.. | # | 001-099 | |
| 0582 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | D12 | | | | GD01906 | ST.. | 2 | 115-199 | |
| 0583 | 22 | | GA | | 3-3 | 34-22-26 | D00083B | E12 | | | | GD01906 | ST.. | # | 115-199 | |
| 0596 | 22 | | GA | | 3-9 | 34-22-26 | D00083B | G06 | | | | GD01909 | ST.. | 2 | 010-099 | |
| 0599 | 22 | | GA | | 3-9 | 34-61-23 | D00177B | J15 | | | | GD01902 | ST.. | 2 | 001-008, 010 | |
| 0599 | 22 | | GA | | 3-9 | 34-61-23 | D00177B | J15 | | | | GD01902 | ST.. | # | 009 | |
| 0601 | 20 | | GA | | 4-0 | 34-58-21 | GD01912 | ST.. | 2 | | | D41393J | | | 002 | |
| 0622 | 22 | | GA | | 0-7 | 22-11-22 | D00075B | J02 | | | | D00075B | J04 | | 001-008 | |
| 0623 | 22 | | GA | | 0-7 | 22-11-22 | D00075B | B12 | | | | D00075B | D15 | | 001-008, 115-199 | |
| 0626 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | C13 | | | | TB0203X | A003 | BJ | 009 | |
| 0626 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | C13 | | | | TB0203X | A004 | BJ | 010-099 | |
| 0627 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | A12 | | | | TB0203X | B004 | BJ | 009-099 | |
| 0628 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | B12 | | | | TB0203X | C004 | BJ | 009-099 | |
| 0629 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | C12 | | | | TB0203X | D003 | BJ | 009-099 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 66

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 0630 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | A13 | | TB0203X | A005 | BJ | | 009-099 |
| 0631 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | B13 | | TB0203X | B005 | BJ | | 009-099 |
| 0632 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | C11 | | TB0203X | C005 | BJ | | 009-099 |
| 0632 | 22 | | PA | | 0-12 | 22-11-22 | D00075B | | C11 | | D00075B | J08 | | | 115-199 |
| 0633 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | F11 | | TB0203X | D006 | BJ | | 009-099 |
| 0634 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | D12 | | TB0203X | A007 | BJ | | 009-099 |
| 0635 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | F12 | | TB0203X | B007 | BJ | | 009-099 |
| 0636 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | H12 | | TB0203X | C007 | BJ | | 009-099 |
| 0637 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | G13 | | TB0203X | D007 | BJ | | 009-099 |
| 0638 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | C10 | | TB0203X | A009 | BJ | | 009-099 |
| 0639 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | D03 | | TB0203X | B009 | BJ | | 009 |
| 0639 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | D03 | | TB0203X | B010 | BJ | | 010-099 |
| 0641 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | A03 | | TB0203X | C010 | BJ | | 009-099 |
| 0642 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | K13 | | TB0203X | D010 | BJ | | 009-099 |
| 0643 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | H13 | | TB0203X | A011 | BJ | | 009-099 |
| 0643 | 22 | | PA | | 0-12 | 22-11-22 | D00075B | | J14 | | D00075B | H13 | | | 115-199 |
| 0644 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | C08 | | TB0203X | B011 | BJ | | 009-099 |
| 0645 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | D04 | | TB0203X | C011 | BJ | | 009-099 |
| 0646 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | J02 | | TB0203X | D012 | BJ | | 009-099 |
| 0647 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | G10 | | TB0203X | A013 | BJ | | 009-099 |
| 0648 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | J10 | | TB0203X | B013 | BJ | | 009-099 |
| 0649 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | G01 | | TB0203X | C013 | BJ | | 009-099 |
| 0650 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | H01 | | TB0203X | D013 | BJ | | 009-099 |
| 0651 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | A04 | | TB0203X | A016 | BJ | | 009-099 |
| 0652 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | F04 | | TB0203X | A004 | BJ | | 009-099 |
| 0653 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | B15 | | TB0203X | B004 | BJ | | 009-099 |
| 0654 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | D15 | | TB0203X | C004 | BJ | | 009-099 |
| 0655 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | E05 | | TB0203X | D004 | BJ | | 009-099 |
| 0657 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | A14 | | TB0203X | A006 | BJ | | 009-099 |
| 0658 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | B14 | | TB0203X | B006 | BJ | | 009-099 |
| 0659 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | J08 | | TB0203X | C006 | BJ | | 009-099 |
| 0660 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | K09 | | TB0203X | D006 | BJ | | 009-099 |
| 0661 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | D14 | | TB0203X | A008 | BJ | | 009-099 |
| 0662 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | K07 | | TB0203X | B008 | BJ | | 009-099 |
| 0663 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | J15 | | TB0203X | C008 | BJ | | 009-099 |
| 0664 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | H14 | | TB0203X | D008 | BJ | | 009-099 |
| 0665 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | C14 | | TB0203X | A010 | BJ | | 009-099 |
| 0666 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | K04 | | TB0203X | B010 | BJ | | 009-099 |
| 0667 | 22 | | GA | | 5-3 | 22-11-23 | D00075B | | E04 | | TB0203X | C010 | BJ | | 009-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 67

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 1122Z | | | | AG | 0-0 | 22-14-11 | D41743J | DED | | | TB0203Z | DED | | | 115-199 |
| 1123 | 22 | GT | | AH | 2-11 | 22-14-11 | D41743J | 8 | | | SM00022 | | WI | | 115-199 |
| 1123Z | | | | AH | 0-0 | 22-14-11 | D41743J | DED | | | SM00022 | DED | | | 115-199 |
| 1124 | 22 | GT | | AL | 2-11 | 22-14-31 | D41393J | 13 | | | SM00019 | | WI | | 115-199 |
| 1124Z | | | | AL | 0-0 | 22-14-31 | D41393J | DED | | | SM00019 | DED | | | 115-199 |
| 1130 | 22 | GT | | CS | 3-5 | 22-14-31 | D41095J | 10 | | | SM00022 | | WI | | 115-199 |
| 1130Z | | | | CS | 0-0 | 22-14-31 | D41095J | DED | | | SM00022 | DED | | | 115-199 |
| 1131 | 22 | GT | | CT | 2-7 | 22-14-31 | D41393J | 15 | | | TB0203Z | 81 | BJ | | 115-199 |
| 1131Z | | | | CT | 0-0 | 22-14-31 | D41393J | DED | | | TB0203Z | DED | | | 115-199 |
| 1132 | 22 | GT | | ER | 2-11 | 22-14-31 | D41393J | 24 | | | SM00014 | | WI | | 115-199 |
| 1132Z | | | | ER | 0-0 | 22-14-31 | D41393J | DED | | | SM00014 | DED | | | 115-199 |
| 1133 | 22 | GT | | FQ | 2-11 | 22-14-31 | D41393J | 16 | | | SM00018 | | WI | | 115-199 |
| 1133Z | | | | FQ | 0-0 | 22-14-31 | D41393J | DED | | | SM00018 | DED | | | 115-199 |
| 1142 | 22 | GT | | GS | 2-11 | 22-14-21 | D41393J | 11 | | | SM00014 | | WI | | 115-199 |
| 1142Z | | | | GS | 0-0 | 22-14-21 | D41393J | DED | | | SM00014 | DED | | | 115-199 |
| 1145 | 22 | GT | | AB | 4-0 | 22-14-21 | D00075B | K03 | | | SM00022 | | WI | | 115-199 |
| 1145Z | | | | AB | 0-0 | 22-14-21 | D00075B | DED | | | SM00022 | DED | | | 115-199 |
| 1146 | 22 | GT | | HG | 3-1 | 22-14-21 | D41095J | 6 | | | D00075B | E12 | | | 115-199 |
| 1146Z | | | | HG | 0-0 | 22-14-21 | D41095J | DED | | | D00075B | DED | | | 115-199 |
| 1147 | 22 | GT | | JF | 3-3 | 22-14-21 | D41393J | 36 | | | D00075A | E12 | | | 115-199 |
| 1147Z | | | | JF | 0-0 | 22-14-21 | D41393J | DED | | | D00075A | DED | | | 115-199 |
| 1148 | 22 | GT | | HP | 3-1 | 22-14-21 | D41095J | 5 | | | D00075A | F01 | | | 115-199 |
| 1148Z | | | | HP | 0-0 | 22-14-21 | D41095J | DED | | | D00075A | DED | | | 115-199 |
| 1150 | 22 | GT | | HQ | 3-3 | 22-15-12 | D41393J | 17 | | | D00075A | K03 | | | 115-199 |
| 1150Z | | | | HQ | 0-0 | 22-15-12 | D41393J | DED | | | D00075A | DED | | | 115-199 |
| 1154 | 22 | GT | | HU | 4-4 | 22-15-12 | D41565J | 48 | | | D00075A | K01 | | | 115-199 |
| 1154Z | | | | HU | 0-0 | 22-15-12 | D41565J | DED | | | D00075A | DED | | | 115-199 |
| 1157 | 22 | GT | | HY | 3-4 | 22-41-13 | D42035J | 23 | | | D00075B | F10 | | | 115-199 |
| 1157Z | | | | HY | 0-0 | 22-41-13 | D42035J | DED | | | D00075B | DED | | | 115-199 |
| 1267 | 22 | GT | | HZ | 2-11 | 22-14-11 | D41743J | 7 | | | SM00019 | | WI | | 115-199 |
| 1267Z | | | | HZ | 0-0 | 22-14-11 | D41743J | DED | | | SM00019 | DED | | | 115-199 |
| 1269 | 22 | GT | | IC | 2-11 | 22-14-11 | D41743J | 14 | | | SM00014 | | WI | | 115-199 |
| 1269Z | | | | IC | 0-0 | 22-14-11 | D41743J | DED | | | SM00014 | DED | | | 115-199 |
| 1287 | 22 | GT | | ID | 3-5 | 22-14-31 | D41095J | 16 | | | SM00022 | | WI | | 115-199 |
| 1287Z | | | | ID | 0-0 | 22-14-31 | D41095J | DED | | | SM00022 | DED | | | 115-199 |
| 1292 | 22 | GT | | KG | 3-1 | 22-41-11 | D00075B | C06 | | | D41095J | 36 | | | 115-199 |
| 1292Z | | | | KG | 0-0 | 22-41-11 | D00075B | DED | | | D41095J | DED | | | 115-199 |
| 1299 | 22 | GT | | JD | 3-1 | 22-15-12 | D41095J | 34 | | | D00075A | G01 | | | 115-199 |
| 1299Z | | | | JD | 0-0 | 22-15-12 | D41095J | DED | | | D00075A | DED | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 69

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 1300 | 22 | GT | JE | | 3-3 | 22-15-12 | D41393J | 40 | | | D00075A | E03 | | | 115-199 |
| 1300Z | | | JE | | 0-0 | 22-15-12 | D41393J | DED | | | D00075A | DED | | | 115-199 |
| 2003B | 22 | GB | KC | | 3-4 | 22-12-21 | D00075B | F13 | | | D41907J | 28 | | | 001-099 |
| 2003B | 22 | GB | KC | | 3-8 | 22-12-21 | D00075B | F13 | | | D41907J | 28 | | | 115-199 |
| 2003R | 22 | GB | KC | | 0-0 | 22-12-21 | D00075B | E13 | | | D41907J | 27 | | | ALL |
| 2009B | 22 | GB | AI | | 2-7 | 22-11-21 | D41624J | 3 | | | TB0203Z | 118 | BJ | | 001-099 |
| 2009B | 22 | GB | AI | | 2-9 | 22-11-21 | D41624J | 3 | | | TB0203Z | 118 | BJ | | 115-199 |
| 2009R | 22 | GB | AI | | 0-0 | 22-11-21 | D41624J | 4 | | | TB0203Z | 117 | BJ | | ALL |
| 2010B | 22 | GB | AJ | | 2-5 | 22-11-21 | D41693J | 5 | | | TB0203Z | 118 | BJ | | 001-099 |
| 2010B | 22 | GB | AJ | | 2-9 | 22-11-21 | D41693J | 5 | | | TB0203Z | 118 | BJ | | 115-199 |
| 2010R | 22 | GB | AJ | | 0-0 | 22-11-21 | D41693J | 6 | | | TB0203Z | 117 | BJ | | ALL |
| 2011B | 22 | GB | AK | | 2-5 | 22-11-21 | D41693J | 7 | | | TB0203Z | 118 | BJ | | 001-099 |
| 2011B | 22 | GB | AK | | 2-9 | 22-11-21 | D41693J | 7 | | | TB0203Z | 118 | BJ | | 115-199 |
| 2011R | 22 | GB | AK | | 0-0 | 22-11-21 | D41693J | 8 | | | TB0203Z | 117 | BJ | | ALL |
| 2012B | 20 | GB | IF | | 2-9 | 22-11-21 | D00075C | 11 | | | TB0203Z | 118 | BJ | | ALL |
| 2012R | 20 | GB | IF | | 0-0 | 22-11-21 | D00075C | 10 | | | TB0203Z | 117 | BJ | | ALL |
| 2017B | 22 | GB | AQ | | 3-3 | 22-12-21 | D00075B | D11 | | | D41693J | 9 | | | 001-099 |
| 2017B | 22 | GB | AQ | | 3-7 | 22-12-21 | D41693J | 9 | | | D00075B | D11 | | | 115-199 |
| 2017R | 22 | GB | AQ | | 0-0 | 22-12-21 | D00075B | E11 | | | D41693J | 10 | | | 001-099 |
| 2017R | 22 | GB | AQ | | 0-0 | 22-12-21 | D41693J | 10 | | | D00075B | E11 | | | 115-199 |
| 2018B | 22 | GB | AR | | 3-4 | 22-13-21 | D00075B | E06 | | | D41624J | 5 | | | 001-099 |
| 2018B | 22 | GB | AR | | 3-7 | 22-13-21 | D41624J | 5 | | | D00075B | E06 | | | 115-199 |
| 2018R | 22 | GB | AR | | 0-0 | 22-13-21 | D00075B | F06 | | | D41624J | 6 | | | 001-099 |
| 2018R | 22 | GB | AR | | 0-0 | 22-13-21 | D41624J | 6 | | | D00075B | F06 | | | 115-199 |
| 2019B | 22 | GB | AS | | 3-3 | 22-13-21 | D00075B | E07 | | | D41693J | 11 | | | 001-099 |
| 2019B | 22 | GB | AS | | 3-7 | 22-13-21 | D41693J | 11 | | | D00075B | E07 | | | 115-199 |
| 2019R | 22 | GB | AS | | 0-0 | 22-13-21 | D00075B | F07 | | | D41693J | 12 | | | 001-099 |
| 2019R | 22 | GB | AS | | 0-0 | 22-13-21 | D41693J | 12 | | | D00075B | F07 | | | 115-199 |
| 2021B | 22 | GB | AU | | 3-3 | 34-31-21 | D00205B | C15 | | | D42107J | 8 | | | 001-099 |
| 2021B | 22 | GB | AU | | 3-7 | 34-31-21 | D42107J | 8 | | | D02941C | 6 | | | 115-199 |
| 2021R | 22 | GB | AU | | 0-0 | 34-31-21 | D00205B | B15 | | | D42107J | 9 | | | 001-099 |
| 2021R | 22 | GB | AU | | 0-0 | 34-31-21 | D42107J | 9 | | | D02941C | 4 | | | 115-199 |
| 2026B | 22 | GB | HN | | 2-5 | 22-11-21 | D41693J | 35 | | | TB0203Z | 118 | BJ | | 001-099 |
| 2026B | 22 | GB | HN | | 2-9 | 22-11-21 | D41693J | 35 | | | TB0203Z | 118 | BJ | | 115-199 |
| 2026R | 22 | GB | HN | | 0-0 | 22-11-21 | D41693J | 34 | | | TB0203Z | 117 | BJ | | ALL |
| 2501T | 24 | BV | AV | | 3-1 | 34-22-24 | D00083E | A01 | | | D41077J | 1 | | | 001-099 |
| 2501T | 24 | BV | AV | | 3-0 | 34-22-24 | D41077J | 1 | | | D00083E | A01 | | | 115-199 |
| 2501W | 24 | BV | AV | | 0-0 | 34-22-24 | D00083E | B01 | | | D41077J | 2 | | | 001-099 |
| 2501W | 24 | BV | AV | | 0-0 | 34-22-24 | D41077J | 2 | | | D00083E | B01 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 70

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1170
Page 71
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 2508T | 24 | BV | BC | | 3-0 | 34-22-24 | D41077J | 22 | | | D00083E | A08 | | | 115-199 |
| 2508W | 24 | BV | BC | | 0-0 | 34-22-24 | D00083E | B08 | | | D41077J | 23 | | | 001-099 |
| 2508W | 24 | BV | BC | | 0-0 | 34-22-24 | D41077J | 23 | | | D00083E | B08 | | | 115-199 |
| 2508Z | | | BC | | 0-0 | 34-22-24 | GD01918 | ST.. | 2 | | D41077J | 24 | | | 001-099 |
| 2508Z | | | BC | | 0-0 | 34-22-24 | D41077J | 24 | | | GD01918 | ST.. | 2 | | 115-199 |
| 2509T | 24 | BV | BD | | 3-1 | 34-22-24 | D00083E | A09 | | | D41077J | 25 | | | 001-099 |
| 2509T | 24 | BV | BD | | 3-0 | 34-22-24 | D41077J | 25 | | | D00083E | A09 | | | 115-199 |
| 2509W | 24 | BV | BD | | 0-0 | 34-22-24 | D00083E | B09 | | | D41077J | 26 | | | 001-099 |
| 2509W | 24 | BV | BD | | 0-0 | 34-22-24 | D41077J | 26 | | | D00083E | B09 | | | 115-199 |
| 2509Z | | | BD | | 0-0 | 34-22-24 | GD01918 | ST.. | 2 | | D41077J | 27 | | | 001-099 |
| 2509Z | | | BD | | 0-0 | 34-22-24 | D41077J | 27 | | | GD01918 | ST.. | 2 | | 115-199 |
| 2510T | 24 | BV | BE | | 3-4 | 34-22-25 | D00083E | C01 | | | D41079J | 1 | | | 001-099 |
| 2510T | 24 | BV | BE | | 3-2 | 34-22-25 | D41079J | 1 | | | D00083E | C01 | | | 115-199 |
| 2510W | 24 | BV | BE | | 0-0 | 34-22-25 | D00083E | D01 | | | D41079J | 2 | | | 001-099 |
| 2510W | 24 | BV | BE | | 0-0 | 34-22-25 | D41079J | 2 | | | D00083E | D01 | | | 115-199 |
| 2510Z | | | BE | | 0-0 | 34-22-25 | GD01918 | ST.. | 2 | | D41079J | 3 | | | 001-099 |
| 2510Z | | | BE | | 0-0 | 34-22-25 | D41079J | 3 | | | GD01918 | ST.. | 2 | | 115-199 |
| 2511T | 24 | BV | BF | | 3-4 | 34-22-25 | D00083E | C02 | | | D41079J | 4 | | | 001-099 |
| 2511T | 24 | BV | BF | | 3-2 | 34-22-25 | D41079J | 4 | | | D00083E | C02 | | | 115-199 |
| 2511W | 24 | BV | BF | | 0-0 | 34-22-25 | D00083E | D02 | | | D41079J | 5 | | | 001-099 |
| 2511W | 24 | BV | BF | | 0-0 | 34-22-25 | D41079J | 5 | | | D00083E | D02 | | | 115-199 |
| 2511Z | | | BF | | 0-0 | 34-22-25 | GD01918 | ST.. | 2 | | D41079J | 6 | | | 001-099 |
| 2511Z | | | BF | | 0-0 | 34-22-25 | D41079J | 6 | | | GD01918 | ST.. | 2 | | 115-199 |
| 2512T | 24 | BV | BG | | 3-4 | 34-22-25 | D00083E | C03 | | | D41079J | 7 | | | 001-099 |
| 2512T | 24 | BV | BG | | 3-2 | 34-22-25 | D41079J | 7 | | | D00083E | C03 | | | 115-199 |
| 2512W | 24 | BV | BG | | 0-0 | 34-22-25 | D00083E | D03 | | | D41079J | 8 | | | 001-099 |
| 2512W | 24 | BV | BG | | 0-0 | 34-22-25 | D41079J | 8 | | | D00083E | D03 | | | 115-199 |
| 2512Z | | | BG | | 0-0 | 34-22-25 | GD01918 | ST.. | 2 | | D41079J | 9 | | | 001-099 |
| 2512Z | | | BG | | 0-0 | 34-22-25 | D41079J | 9 | | | GD01918 | ST.. | 2 | | 115-199 |
| 2513T | 24 | BV | BH | | 3-4 | 34-22-25 | D00083E | C04 | | | D41079J | 10 | | | 001-099 |
| 2513T | 24 | BV | BH | | 3-2 | 34-22-25 | D41079J | 10 | | | D00083E | C04 | | | 115-199 |
| 2513W | 24 | BV | BH | | 0-0 | 34-22-25 | D00083E | D04 | | | D41079J | 11 | | | 001-099 |
| 2513W | 24 | BV | BH | | 0-0 | 34-22-25 | D41079J | 11 | | | D00083E | D04 | | | 115-199 |
| 2513Z | | | BH | | 0-0 | 34-22-25 | GD01919 | ST.. | 2 | | D41079J | 12 | | | 001-099 |
| 2513Z | | | BH | | 0-0 | 34-22-25 | D41079J | 12 | | | GD01919 | ST.. | 2 | | 115-199 |
| 2514T | 24 | BV | B1 | | 3-4 | 34-22-25 | D00083E | C05 | | | D41079J | 13 | | | 001-099 |
| 2514T | 24 | BV | B1 | | 3-2 | 34-22-25 | D41079J | 13 | | | D00083E | C05 | | | 115-199 |
| 2514W | 24 | BV | B1 | | 0-0 | 34-22-25 | D00083E | D05 | | | D41079J | 14 | | | 001-099 |
| 2514W | 24 | BV | B1 | | 0-0 | 34-22-25 | D41079J | 14 | | | D00083E | D05 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 72

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1170
Page 73
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 2521T | 24 | BV | BP | | 2-11 | 34-22-34 | D40881J | 7 | | | D00083B | A09 | | | 115-199 |
| 2521W | 24 | BV | BP | | 0-0 | 34-22-34 | D00083B | B09 | | | D40881J | 8 | | | 001-099 |
| 2521W | 24 | BV | BP | | 0-0 | 34-22-34 | D40881J | 8 | | | D00083B | B09 | | | 115-199 |
| 2521Z | | | BP | | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 9 | | | 001-099 |
| 2521Z | | | BP | | 0-0 | 34-22-34 | D40881J | 9 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2522T | 24 | BV | BQ | | 2-11 | 34-22-34 | D00083B | A10 | | | D40881J | 10 | | | 001-099 |
| 2522T | 24 | BV | BQ | | 2-11 | 34-22-34 | D40881J | 10 | | | D00083B | A10 | | | 115-199 |
| 2522W | 24 | BV | BQ | | 0-0 | 34-22-34 | D00083B | B10 | | | D40881J | 11 | | | 001-099 |
| 2522W | 24 | BV | BQ | | 0-0 | 34-22-34 | D40881J | 11 | | | D00083B | B10 | | | 115-199 |
| 2522Z | | | BQ | | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 12 | | | 001-099 |
| 2522Z | | | BQ | | 0-0 | 34-22-34 | D40881J | 12 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2523T | 24 | BV | BR | | 2-11 | 34-22-34 | D00083B | A11 | | | D40881J | 13 | | | 001-099 |
| 2523T | 24 | BV | BR | | 2-11 | 34-22-34 | D40881J | 13 | | | D00083B | A11 | | | 115-199 |
| 2523W | 24 | BV | BR | | 0-0 | 34-22-34 | D00083B | B11 | | | D40881J | 14 | | | 001-099 |
| 2523W | 24 | BV | BR | | 0-0 | 34-22-34 | D40881J | 14 | | | D00083B | B11 | | | 115-199 |
| 2523Z | | | BR | | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 15 | | | 001-099 |
| 2523Z | | | BR | | 0-0 | 34-22-34 | D40881J | 15 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2524T | 24 | BV | BS | | 2-11 | 34-22-34 | D00083B | A12 | | | D40881J | 16 | | | 001-099 |
| 2524T | 24 | BV | BS | | 2-11 | 34-22-34 | D40881J | 16 | | | D00083B | A12 | | | 115-199 |
| 2524W | 24 | BV | BS | | 0-0 | 34-22-34 | D00083B | B12 | | | D40881J | 17 | | | 001-099 |
| 2524W | 24 | BV | BS | | 0-0 | 34-22-34 | D40881J | 17 | | | D00083B | B12 | | | 115-199 |
| 2524Z | | | BS | | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 18 | | | 001-099 |
| 2524Z | | | BS | | 0-0 | 34-22-34 | D40881J | 18 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2525T | 24 | BV | BT | | 2-11 | 34-22-34 | D00083B | A13 | | | D40881J | 19 | | | 001-099 |
| 2525T | 24 | BV | BT | | 2-11 | 34-22-34 | D40881J | 19 | | | D00083B | A13 | | | 115-199 |
| 2525W | 24 | BV | BT | | 0-0 | 34-22-34 | D00083B | B13 | | | D40881J | 20 | | | 001-099 |
| 2525W | 24 | BV | BT | | 0-0 | 34-22-34 | D40881J | 20 | | | D00083B | B13 | | | 115-199 |
| 2525Z | | | BT | | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 21 | | | 001-099 |
| 2525Z | | | BT | | 0-0 | 34-22-34 | D40881J | 21 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2526T | 24 | BV | BU | | 2-11 | 34-22-34 | D00083B | A14 | | | D40881J | 22 | | | 001-099 |
| 2526T | 24 | BV | BU | | 2-11 | 34-22-34 | D40881J | 22 | | | D00083B | A14 | | | 115-199 |
| 2526W | 24 | BV | BU | | 0-0 | 34-22-34 | D00083B | B14 | | | D40881J | 23 | | | 001-099 |
| 2526W | 24 | BV | BU | | 0-0 | 34-22-34 | D40881J | 23 | | | D00083B | B14 | | | 115-199 |
| 2526Z | | | BU | | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 24 | | | 001-099 |
| 2526Z | | | BU | | 0-0 | 34-22-34 | D40881J | 24 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2527T | 24 | BV | BV | | 2-11 | 34-22-34 | D00083B | A15 | | | D40881J | 25 | | | 001-099 |
| 2527T | 24 | BV | BV | | 2-11 | 34-22-34 | D40881J | 25 | | | D00083B | A15 | | | 115-199 |
| 2527W | 24 | BV | BV | | 0-0 | 34-22-34 | D00083B | B15 | | | D40881J | 26 | | | 001-099 |
| 2527W | 24 | BV | BV | | 0-0 | 34-22-34 | D40881J | 26 | | | D00083B | B15 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 74

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 2527Z | | | | BV | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 27 | | | 001-099 |
| 2527Z | | | | BV | 0-0 | 34-22-34 | D40881J | 27 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2528T | 24 | | BV | BW | 2-11 | 34-22-34 | D00083B | J07 | | | D40881J | 28 | | | 001-099 |
| 2528T | 24 | | BV | BW | 2-11 | 34-22-34 | D40881J | 28 | | | D00083B | J07 | | | 115-199 |
| 2528W | 24 | | BV | BW | 0-0 | 34-22-34 | D00083B | K07 | | | D40881J | 29 | | | 001-099 |
| 2528W | 24 | | BV | BW | 0-0 | 34-22-34 | D40881J | 29 | | | D00083B | K07 | | | 115-199 |
| 2528Z | | | | BW | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 30 | | | 001-099 |
| 2528Z | | | | BW | 0-0 | 34-22-34 | D40881J | 30 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2529T | 24 | | BV | BX | 2-11 | 34-22-34 | D00083B | J08 | | | D40881J | 31 | | | 001-099 |
| 2529T | 24 | | BV | BX | 2-11 | 34-22-34 | D40881J | 31 | | | D00083B | J08 | | | 115-199 |
| 2529W | 24 | | BV | BX | 0-0 | 34-22-34 | D00083B | K08 | | | D40881J | 32 | | | 001-099 |
| 2529W | 24 | | BV | BX | 0-0 | 34-22-34 | D40881J | 32 | | | D00083B | K08 | | | 115-199 |
| 2529Z | | | | BX | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 33 | | | 001-099 |
| 2529Z | | | | BX | 0-0 | 34-22-34 | D40881J | 33 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2530T | 24 | | BV | BY | 2-11 | 34-22-34 | D00083B | J09 | | | D40881J | 34 | | | 001-099 |
| 2530T | 24 | | BV | BY | 2-11 | 34-22-34 | D40881J | 34 | | | D00083B | J09 | | | 115-199 |
| 2530W | 24 | | BV | BY | 0-0 | 34-22-34 | D00083B | K09 | | | D40881J | 35 | | | 001-099 |
| 2530W | 24 | | BV | BY | 0-0 | 34-22-34 | D40881J | 35 | | | D00083B | K09 | | | 115-199 |
| 2530Z | | | | BY | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 36 | | | 001-099 |
| 2530Z | | | | BY | 0-0 | 34-22-34 | D40881J | 36 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2531T | 24 | | BV | BZ | 2-11 | 34-22-34 | D00083B | J10 | | | D40881J | 37 | | | 001-099 |
| 2531T | 24 | | BV | BZ | 2-11 | 34-22-34 | D40881J | 37 | | | D00083B | J10 | | | 115-199 |
| 2531W | 24 | | BV | BZ | 0-0 | 34-22-34 | D00083B | K10 | | | D40881J | 38 | | | 001-099 |
| 2531W | 24 | | BV | BZ | 0-0 | 34-22-34 | D40881J | 38 | | | D00083B | K10 | | | 115-199 |
| 2531Z | | | | BZ | 0-0 | 34-22-34 | GD01917 | ST.. | 2 | | D40881J | 39 | | | 001-099 |
| 2531Z | | | | BZ | 0-0 | 34-22-34 | D40881J | 39 | | | GD01917 | ST.. | 2 | | 115-199 |
| 2532T | 24 | | BV | CA | 2-11 | 34-22-34 | D00083B | J11 | | | D40881J | 40 | | | 001-099 |
| 2532T | 24 | | BV | CA | 2-11 | 34-22-34 | D40881J | 40 | | | D00083B | J11 | | | 115-199 |
| 2532W | 24 | | BV | CA | 0-0 | 34-22-34 | D00083B | K11 | | | D40881J | 41 | | | 001-099 |
| 2532W | 24 | | BV | CA | 0-0 | 34-22-34 | D40881J | 41 | | | D00083B | K11 | | | 115-199 |
| 2532Z | | | | CA | 0-0 | 34-22-34 | GD01919 | ST.. | 2 | | D40881J | 42 | | | 001-099 |
| 2532Z | | | | CA | 0-0 | 34-22-34 | D40881J | 42 | | | GD01919 | ST.. | 2 | | 115-199 |
| 2533T | 24 | | BV | CB | 2-11 | 34-22-34 | D00083B | J12 | | | D40881J | 43 | | | 001-099 |
| 2533T | 24 | | BV | CB | 2-11 | 34-22-34 | D40881J | 43 | | | D00083B | J12 | | | 115-199 |
| 2533W | 24 | | BV | CB | 0-0 | 34-22-34 | D00083B | K12 | | | D40881J | 44 | | | 001-099 |
| 2533W | 24 | | BV | CB | 0-0 | 34-22-34 | D40881J | 44 | | | D00083B | K12 | | | 115-199 |
| 2533Z | | | | CB | 0-0 | 34-22-34 | GD01919 | ST.. | 2 | | D40881J | 45 | | | 001-099 |
| 2533Z | | | | CB | 0-0 | 34-22-34 | D40881J | 45 | | | GD01919 | ST.. | 2 | | 115-199 |
| 2534T | 24 | | BV | CC | 2-11 | 34-22-34 | D00083B | J13 | | | D40881J | 46 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 75

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | |
| 2534T | 24 | BV | CC | | 2-11 | 34-22-34 | D40881J | 46 | | | D00083B | J13 | | | 115-199 |
| 2534W | 24 | BV | CC | | 0-0 | 34-22-34 | D00083B | K13 | | | D40881J | 47 | | | 001-099 |
| 2534W | 24 | BV | CC | | 0-0 | 34-22-34 | D40881J | 47 | | | D00083B | K13 | | | 115-199 |
| 2534Z | | | CC | | 0-0 | 34-22-34 | GD01919 | ST.. | 2 | | D40881J | 48 | | | 001-099 |
| 2534Z | | | CC | | 0-0 | 34-22-34 | D40881J | 48 | | | GD01919 | ST.. | 2 | | 115-199 |
| 2535T | 24 | BV | CD | | 2-11 | 34-22-34 | D00083B | J14 | | | D40881J | 49 | | | 001-099 |
| 2535T | 24 | BV | CD | | 2-11 | 34-22-34 | D40881J | 49 | | | D00083B | J14 | | | 115-199 |
| 2535W | 24 | BV | CD | | 0-0 | 34-22-34 | D00083B | K14 | | | D40881J | 50 | | | 001-099 |
| 2535W | 24 | BV | CD | | 0-0 | 34-22-34 | D40881J | 50 | | | D00083B | K14 | | | 115-199 |
| 2535Z | | | CD | | 0-0 | 34-22-34 | GD01919 | ST.. | 2 | | D40881J | 51 | | | 001-099 |
| 2535Z | | | CD | | 0-0 | 34-22-34 | D40881J | 51 | | | GD01919 | ST.. | 2 | | 115-199 |
| 2536T | 24 | BV | CE | | 2-11 | 34-22-34 | D00083B | J15 | | | D40881J | 52 | | | 001-099 |
| 2536T | 24 | BV | CE | | 2-11 | 34-22-34 | D40881J | 52 | | | D00083B | J15 | | | 115-199 |
| 2536W | 24 | BV | CE | | 0-0 | 34-22-34 | D00083B | K15 | | | D40881J | 53 | | | 001-099 |
| 2536W | 24 | BV | CE | | 0-0 | 34-22-34 | D40881J | 53 | | | D00083B | K15 | | | 115-199 |
| 2536Z | | | CE | | 0-0 | 34-22-34 | GD01919 | ST.. | 2 | | D40881J | 54 | | | 001-099 |
| 2536Z | | | CE | | 0-0 | 34-22-34 | D40881J | 54 | | | GD01919 | ST.. | 2 | | 115-199 |
| 2537B | 24 | G2 | HL | | 2-10 | 73-21-22 | D41431J | 5 | | | TB0203Y | A107 | BJ | | 001-099 |
| 2537B | 24 | G2 | HL | | 2-3 | 73-21-22 | D41431J | 23 | | | TB0203Y | A107 | BJ | | 115-199 |
| 2537R | 24 | G2 | HL | | 0-0 | 73-21-22 | D41431J | 6 | | | TB0203Y | A108 | BJ | | 001-099 |
| 2537R | 24 | G2 | HL | | 0-0 | 73-21-22 | D41431J | 24 | | | TB0203Y | A108 | BJ | | 115-199 |
| 2537Z | | | HL | | 0-0 | 73-21-22 | D41431J | 7 | | | GD01915 | ST.. | 2 | | 001-099 |
| 2537Z | | | HL | | 0-0 | 73-21-22 | D41431J | 25 | | | GD01915 | ST.. | 2 | | 115-199 |
| 2538B | 24 | G2 | HM | | 4-2 | 73-21-12 | D41393J | 34 | | | TB0203Y | C029 | BJ | | 001-099 |
| 2538B | 24 | G2 | HM | | 3-10 | 73-21-12 | D41393J | 34 | | | TB0203Y | C029 | BJ | | 115-199 |
| 2538R | 24 | G2 | HM | | 0-0 | 73-21-12 | D41393J | 33 | | | TB0203Y | A029 | BJ | | ALL |
| 2538Z | | | HM | | 0-0 | 73-21-12 | D41393J | 35 | | | GD01906 | ST.. | 2 | | ALL |
| 2539B | 24 | G2 | IY | | 3-4 | 73-21-12 | D00291B | B06 | | | TB0203Y | C028 | BJ | | 001-099 |
| 2539B | 24 | G2 | IT | | 3-4 | 73-21-12 | D00291B | B06 | | | TB0203Y | C028 | BJ | | 115-199 |
| 2539R | 24 | G2 | IY | | 0-0 | 73-21-12 | D00291B | A06 | | | TB0203Y | A028 | BJ | | 001-099 |
| 2539R | 24 | G2 | IT | | 0-0 | 73-21-12 | D00291B | A06 | | | TB0203Y | A028 | BJ | | 115-199 |
| 2539Z | | | IY | | 0-0 | 73-21-12 | D00291B | DED | | | GD01906 | ST.. | 2 | | 001-099 |
| 2539Z | | | IT | | 0-0 | 73-21-12 | D00291B | DED | | | GD01906 | ST.. | 2 | | 115-199 |
| 2540B | 24 | G2 | FR | | 4-6 | 23-51-13 | D00205B | B01 | | | D41347J | 10 | | | 001-099 |
| 2540B | 24 | G2 | FR | | 4-5 | 23-51-13 | D41347J | 10 | | | D02941B | K10 | | | 115-199 |
| 2540R | 24 | G2 | FR | | 0-0 | 23-51-13 | D00205B | A01 | | | D41347J | 9 | | | 001-099 |
| 2540R | 24 | G2 | FR | | 0-0 | 23-51-13 | D41347J | 9 | | | D02941B | J10 | | | 115-199 |
| 2540Z | | | FR | | 0-0 | 23-51-13 | D00205B | DED | | | D41347J | 11 | | | 001-099 |
| 2540Z | | | FR | | 0-0 | 23-51-13 | D41347J | 11 | | | D02941B | DED | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 76

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | |
| 3001B | 24 | GM | CF | | 3-6 | 34-12-21 | D42085J | 20 | | | SM00026 | | WI | | 001-099 |
| 3001B | 24 | GM | CF | | 2-8 | 34-12-21 | D42085J | 20 | | | D00291B | J12 | | | 115-199 |
| 3001R | 24 | GM | CF | | 0-0 | 34-12-21 | D42085J | 19 | | | SM00021 | | WI | | 001-099 |
| 3001R | 24 | GM | CF | | 0-0 | 34-12-21 | D42085J | 19 | | | D00291B | H12 | | | 115-199 |
| 3001Y | 24 | GM | CF | | 0-0 | 34-12-21 | D42085J | 21 | | | SM00034 | | WI | | 001-099 |
| 3001Y | 24 | GM | CF | | 0-0 | 34-12-21 | D42085J | 21 | | | D00291B | K12 | | | 115-199 |
| 3002B | 24 | GM | CG | | 6-6 | 34-12-21 | D42035J | 19 | | | D00291B | J11 | | | 115-199 |
| 3002R | 24 | GM | CG | | 0-0 | 34-12-21 | D42035J | 18 | | | D00291B | H11 | | | 115-199 |
| 3002Y | 24 | GM | CG | | 0-0 | 34-12-21 | D42035J | 20 | | | D00291B | K11 | | | 115-199 |
| 3003B | 24 | GM | CH | | 6-6 | 34-12-21 | D00291B | J10 | | | D42035J | 25 | | | 001-099 |
| 3003B | 24 | GM | CH | | 6-6 | 34-12-21 | D42035J | 25 | | | D00291B | J10 | | | 115-199 |
| 3003R | 24 | GM | CH | | 0-0 | 34-12-21 | D00291B | H10 | | | D42035J | 24 | | | 001-099 |
| 3003R | 24 | GM | CH | | 0-0 | 34-12-21 | D42035J | 24 | | | D00291B | H10 | | | 115-199 |
| 3003Y | 24 | GM | CH | | 0-0 | 34-12-21 | D00291B | K10 | | | D42035J | 26 | | | 001-099 |
| 3003Y | 24 | GM | CH | | 0-0 | 34-12-21 | D42035J | 26 | | | D00291B | K10 | | | 115-199 |
| 3004B | 24 | GM | CI | | 2-8 | 34-12-21 | D00291B | J02 | | | D42143J | 4 | | | 001-099 |
| 3004B | 24 | GM | CI | | 2-8 | 34-12-21 | D42143J | 4 | | | D00291B | J02 | | | 115-199 |
| 3004R | 24 | GM | CI | | 0-0 | 34-12-21 | D00291B | H02 | | | D42143J | 3 | | | 001-099 |
| 3004R | 24 | GM | CI | | 0-0 | 34-12-21 | D42143J | 3 | | | D00291B | H02 | | | 115-199 |
| 3004Y | 24 | GM | CI | | 0-0 | 34-12-21 | D00291B | K02 | | | D42143J | 5 | | | 001-099 |
| 3004Y | 24 | GM | CI | | 0-0 | 34-12-21 | D42143J | 5 | | | D00291B | K02 | | | 115-199 |
| 3005B | 24 | GM | CJ | | 2-8 | 34-12-21 | D00291B | J04 | | | D42143J | 10 | | | 001-099 |
| 3005B | 24 | GM | CJ | | 2-8 | 34-12-21 | D42143J | 10 | | | D00291B | J04 | | | 115-199 |
| 3005R | 24 | GM | CJ | | 0-0 | 34-12-21 | D00291B | H04 | | | D42143J | 11 | | | 001-099 |
| 3005R | 24 | GM | CJ | | 0-0 | 34-12-21 | D42143J | 11 | | | D00291B | H04 | | | 115-199 |
| 3005Y | 24 | GM | CJ | | 0-0 | 34-12-21 | D00291B | K04 | | | D42143J | 12 | | | 001-099 |
| 3005Y | 24 | GM | CJ | | 0-0 | 34-12-21 | D42143J | 12 | | | D00291B | K04 | | | 115-199 |
| 3006B | 22 | GC | CK | | 3-3 | 22-12-21 | D00075A | H10 | | | D41693J | 13 | | | 001-099 |
| 3006B | 22 | GC | CK | | 3-7 | 22-12-21 | D41693J | 13 | | | D00075A | H10 | | | 115-199 |
| 3006R | 22 | GC | CK | | 0-0 | 22-12-21 | D00075A | J09 | | | D41693J | 4 | | | 001-099 |
| 3006R | 22 | GC | CK | | 0-0 | 22-12-21 | D41693J | 4 | | | D00075A | J09 | | | 115-199 |
| 3006Y | 22 | GC | CK | | 0-0 | 22-12-21 | D00075A | H09 | | | D41693J | 15 | | | 001-099 |
| 3006Y | 22 | GC | CK | | 0-0 | 22-12-21 | D41693J | 15 | | | D00075A | H09 | | | 115-199 |
| 3007B | 22 | GC | CL | | 3-3 | 22-12-21 | D00075B | H10 | | | D41693J | 16 | | | 001-099 |
| 3007B | 22 | GC | CL | | 3-7 | 22-12-21 | D41693J | 16 | | | D00075B | H10 | | | 115-199 |
| 3007R | 22 | GC | CL | | 0-0 | 22-12-21 | D00075B | J09 | | | D41693J | 2 | | | 001-099 |
| 3007R | 22 | GC | CL | | 0-0 | 22-12-21 | D41693J | 2 | | | D00075B | J09 | | | 115-199 |
| 3007Y | 22 | GC | CL | | 0-0 | 22-12-21 | D00075B | H09 | | | D41693J | 18 | | | 001-099 |
| 3007Y | 22 | GC | CL | | 0-0 | 22-12-21 | D41693J | 18 | | | D00075B | H09 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 77

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|-----|-----------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | | |
| 3010B | 22 | GC | CO | | 3-4 | 22-13-21 | D00075B | K06 | | | D41624J | 10 | | | 001-099 | | |
| 3010B | 22 | GC | CO | | 3-7 | 22-13-21 | D41624J | 10 | | | D00075B | K06 | | | 115-199 | | |
| 3010R | 22 | GC | CO | | 0-0 | 22-13-21 | D00075B | J05 | | | D41624J | 11 | | | 001-099 | | |
| 3010R | 22 | GC | CO | | 0-0 | 22-13-21 | D41624J | 11 | | | D00075B | J05 | | | 115-199 | | |
| 3010Y | 22 | GC | CO | | 0-0 | 22-13-21 | D00075B | K05 | | | D41624J | 12 | | | 001-099 | | |
| 3010Y | 22 | GC | CO | | 0-0 | 22-13-21 | D41624J | 12 | | | D00075B | K05 | | | 115-199 | | |
| 3011B | 22 | GC | CP | | 3-4 | 22-13-21 | D00075A | K06 | | | D41624J | 7 | | | 001-099 | | |
| 3011B | 22 | GC | CP | | 3-7 | 22-13-21 | D41624J | 7 | | | D00075A | K06 | | | 115-199 | | |
| 3011R | 22 | GC | CP | | 0-0 | 22-13-21 | D00075A | J05 | | | D41624J | 8 | | | 001-099 | | |
| 3011R | 22 | GC | CP | | 0-0 | 22-13-21 | D41624J | 8 | | | D00075A | J05 | | | 115-199 | | |
| 3011Y | 22 | GC | CP | | 0-0 | 22-13-21 | D00075A | K05 | | | D41624J | 9 | | | 001-099 | | |
| 3011Y | 22 | GC | CP | | 0-0 | 22-13-21 | D41624J | 9 | | | D00075A | K05 | | | 115-199 | | |
| 3012B | 22 | GC | CQ | | 3-3 | 22-13-21 | D00075A | J06 | | | D41693J | 3 | | | 001-099 | | |
| 3012B | 22 | GC | CQ | | 3-7 | 22-13-21 | D41693J | 3 | | | D00075A | J06 | | | 115-199 | | |
| 3012R | 22 | GC | CQ | | 0-0 | 22-13-21 | D00075A | H06 | | | D41693J | 20 | | | 001-099 | | |
| 3012R | 22 | GC | CQ | | 0-0 | 22-13-21 | D41693J | 20 | | | D00075A | H06 | | | 115-199 | | |
| 3012Y | 22 | GC | CQ | | 0-0 | 22-13-21 | D00075A | H05 | | | D41693J | 21 | | | 001-099 | | |
| 3012Y | 22 | GC | CQ | | 0-0 | 22-13-21 | D41693J | 21 | | | D00075A | H05 | | | 115-199 | | |
| 3013B | 22 | GC | CR | | 3-3 | 22-13-21 | D00075B | J06 | | | D41693J | 22 | | | 001-099 | | |
| 3013B | 22 | GC | CR | | 3-7 | 22-13-21 | D41693J | 22 | | | D00075B | J06 | | | 115-199 | | |
| 3013R | 22 | GC | CR | | 0-0 | 22-13-21 | D00075B | H06 | | | D41693J | 23 | | | 001-099 | | |
| 3013R | 22 | GC | CR | | 0-0 | 22-13-21 | D41693J | 23 | | | D00075B | H06 | | | 115-199 | | |
| 3013Y | 22 | GC | CR | | 0-0 | 22-13-21 | D00075B | H05 | | | D41693J | 24 | | | 001-099 | | |
| 3013Y | 22 | GC | CR | | 0-0 | 22-13-21 | D41693J | 24 | | | D00075B | H05 | | | 115-199 | | |
| 3016B | 24 | GM | KH | | 4-3 | 34-12-21 | D00291B | J12 | | | SM00026 | | WI | | 001-099 | | |
| 3016R | 24 | GM | KH | | 0-0 | 34-12-21 | D00291B | H12 | | | SM00021 | | WI | | 001-099 | | |
| 3016Y | 24 | GM | KH | | 0-0 | 34-12-21 | D00291B | K12 | | | SM00034 | | WI | | 001-099 | | |
| 3017B | 24 | GM | KI | | 4-3 | 34-12-21 | D00291B | J11 | | | SM00026 | | WI | | 001-099 | | |
| 3017R | 24 | GM | KI | | 0-0 | 34-12-21 | D00291B | H11 | | | SM00021 | | WI | | 001-099 | | |
| 3017Y | 24 | GM | KI | | 0-0 | 34-12-21 | D00291B | K11 | | | SM00034 | | WI | | 001-099 | | |
| 3019B | 22 | GC | IB | | 3-3 | 22-12-21 | D00075B | D05 | | | D41693J | 37 | | | 001-099 | | |
| 3019B | 22 | GC | IB | | 3-7 | 22-12-21 | D41693J | 37 | | | D00075B | D05 | | | 115-199 | | |
| 3019R | 22 | GC | IB | | 0-0 | 22-12-21 | D00075B | C05 | | | D41693J | 36 | | | 001-099 | | |
| 3019R | 22 | GC | IB | | 0-0 | 22-12-21 | D41693J | 36 | | | D00075B | C05 | | | 115-199 | | |
| 3019Y | 22 | GC | IB | | 0-0 | 22-12-21 | D00075B | D06 | | | D41693J | 38 | | | 001-099 | | |
| 3019Y | 22 | GC | IB | | 0-0 | 22-12-21 | D41693J | 38 | | | D00075B | D06 | | | 115-199 | | |
| 5001B | 24 | G2 | CU | | 3-6 | 34-22-18 | D41603J | 2 | | | TB0203Z | 85 | BJ | | 001-099 | | |
| 5001B | 24 | G2 | CU | | 3-6 | 34-22-18 | D41603J | 2 | | | TB0203Y | A090 | BJ | | 115-199 | | |
| 5001R | 24 | G2 | CU | | 0-0 | 34-22-18 | D41603J | 1 | | | TB0203Z | 86 | BJ | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 78

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5001R | 24 | G2 | CU | | 0-0 | 34-22-18 | D41603J | 1 | | | TB0203Y | A091 | BJ | | 115-199 |
| 5001Z | | | CU | | 0-0 | 34-22-18 | D41603J | 3 | | | GD01912 | ST.. | 2 | | ALL |
| 5002B | 24 | G2 | CV | | 4-6 | 34-22-28 | D00083D | B03 | | | TB0203Z | 85 | BJ | | 001-099 |
| 5002B | 24 | G2 | CV | | 4-6 | 34-22-28 | D00083D | B03 | | | TB0203Y | A090 | BJ | | 115-199 |
| 5002R | 24 | G2 | CV | | 0-0 | 34-22-28 | D00083D | A03 | | | TB0203Z | 86 | BJ | | 001-099 |
| 5002R | 24 | G2 | CV | | 0-0 | 34-22-28 | D00083D | A03 | | | TB0203Y | A091 | BJ | | 115-199 |
| 5002Z | | | CV | | 0-0 | 34-22-28 | D00083D | DED | | | GD01912 | ST.. | 2 | | ALL |
| 5003B | 24 | G2 | CW | | 3-10 | 34-61-25 | D00177A | B11 | | | TB0203Z | 85 | BJ | | 001-099 |
| 5003B | 24 | G2 | CW | | 3-10 | 34-61-25 | D00177A | B11 | | | TB0203Y | A090 | BJ | | 115-199 |
| 5003R | 24 | G2 | CW | | 0-0 | 34-61-25 | D00177A | A11 | | | TB0203Z | 86 | BJ | | 001-099 |
| 5003R | 24 | G2 | CW | | 0-0 | 34-61-25 | D00177A | A11 | | | TB0203Y | A091 | BJ | | 115-199 |
| 5003Z | | | CW | | 0-0 | 34-61-25 | D00177A | DED | | | GD01912 | ST.. | 2 | | ALL |
| 5004B | 24 | G2 | CX | | 2-4 | 34-22-38 | D41679J | 12 | | | TB0203Z | 85 | BJ | | 001-099 |
| 5004B | 24 | G2 | CX | | 2-6 | 34-22-38 | D41679J | 12 | | | TB0203Y | A090 | BJ | | 115-199 |
| 5004R | 24 | G2 | CX | | 0-0 | 34-22-38 | D41679J | 11 | | | TB0203Z | 86 | BJ | | 001-099 |
| 5004R | 24 | G2 | CX | | 0-0 | 34-22-38 | D41679J | 11 | | | TB0203Y | A091 | BJ | | 115-199 |
| 5004Z | | | CX | | 0-0 | 34-22-38 | D41679J | 13 | | | GD01912 | ST.. | 2 | | ALL |
| 5005B | 24 | G2 | CY | | 3-2 | 34-22-24 | D41077J | 31 | | | TB0203Z | 58 | BJ | | 001-099 |
| 5005B | 24 | G2 | CY | | 3-1 | 34-22-24 | D41077J | 31 | | | TB0203Z | 58 | BJ | | 115-199 |
| 5005R | 24 | G2 | CY | | 0-0 | 34-22-24 | D41077J | 32 | | | TB0203Z | 59 | BJ | | ALL |
| 5005Z | | | CY | | 0-0 | 34-22-24 | D41077J | 33 | | | GD01908 | ST.. | 2 | | ALL |
| 5006B | 24 | G2 | CZ | | 3-5 | 34-22-24 | D00083D | F05 | | | TB0203Z | 58 | BJ | | ALL |
| 5006R | 24 | G2 | CZ | | 0-0 | 34-22-24 | D00083D | E05 | | | TB0203Z | 59 | BJ | | ALL |
| 5006Z | | | CZ | | 0-0 | 34-22-24 | D00083D | DED | | | GD01908 | ST.. | 2 | | ALL |
| 5007B | 24 | G2 | DA | | 2-4 | 34-43-11 | D41063J | 12 | | | TB0203Z | 58 | BJ | | 001, 003-099 |
| 5007B | 24 | G2 | DA | | 2-8 | 34-43-11 | D41063J | 12 | | | TB0203Z | 58 | BJ | | 115-199 |
| 5007R | 24 | G2 | DA | | 0-0 | 34-43-11 | D41063J | 11 | | | TB0203Z | 59 | BJ | | 001, 003-099, 115-199 |
| 5007Z | | | DA | | 0-0 | 34-43-11 | D41063J | 13 | | | GD01908 | ST.. | 2 | | 001, 003-099, 115-199 |
| 5008B | 24 | G2 | DB | | 2-5 | 34-22-34 | D41603J | 39 | | | TB0203Z | 58 | BJ | | ALL |
| 5008R | 24 | G2 | DB | | 0-0 | 34-22-34 | D41603J | 38 | | | TB0203Z | 59 | BJ | | ALL |
| 5008Z | | | DB | | 0-0 | 34-22-34 | D41603J | 40 | | | GD01908 | ST.. | 2 | | ALL |
| 5009B | 24 | G2 | DC | | 2-10 | 34-61-24 | D00177A | B05 | | | TB0203Z | 58 | BJ | | ALL |
| 5009R | 24 | G2 | DC | | 0-0 | 34-61-24 | D00177A | A05 | | | TB0203Z | 59 | BJ | | ALL |
| 5009Z | | | DC | | 0-0 | 34-61-24 | D00177A | DED | | | GD01908 | ST.. | 2 | | ALL |
| 5010B | 24 | G2 | DD | | 3-3 | 34-31-21 | D00205B | C11 | | | TB0203Y | C090 | BJ | | 001-099 |
| 5010B | 24 | G2 | DD | | 3-3 | 34-31-21 | D02941B | H01 | | | TB0203Y | C090 | BJ | | 115-199 |
| 5010R | 24 | G2 | DD | | 0-0 | 34-31-21 | D00205B | B11 | | | TB0203Y | C091 | BJ | | 001-099 |
| 5010R | 24 | G2 | DD | | 0-0 | 34-31-21 | D02941B | G01 | | | TB0203Y | C091 | BJ | | 115-199 |
| 5010Z | | | DD | | 0-0 | 34-31-21 | D00205B | DED | | | GD01913 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 79

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5010Z | | | | DD | 0-0 | 34-31-21 | D02941B | DED | | | GD01913 | ST.. | 2 | | 115-199 |
| 5011B | 24 | G2 | DE | | 4-0 | 34-22-28 | D00083A | B03 | | | D41565J | 36 | | | 001-099 |
| 5011B | 24 | G2 | DE | | 4-0 | 34-22-28 | D41565J | 36 | | | D00083A | B03 | | | 115-199 |
| 5011R | 24 | G2 | DE | | 0-0 | 34-22-28 | D00083A | A03 | | | D41565J | 35 | | | 001-099 |
| 5011R | 24 | G2 | DE | | 0-0 | 34-22-28 | D41565J | 35 | | | D00083A | A03 | | | 115-199 |
| 5011Z | | | DE | | 0-0 | 34-22-28 | D00083A | DED | | | D41565J | | | AA | 001-099 |
| 5011Z | | | DE | | 0-0 | 34-22-28 | D41565J | | | AA | D00083A | DED | | | 115-199 |
| 5012B | 24 | G2 | DF | | 4-0 | 34-22-29 | D00083B | H04 | | | D41345J | 46 | | | 001-099 |
| 5012B | 24 | G2 | DF | | 4-1 | 34-22-29 | D41345J | 46 | | | D00083B | H04 | | | 115-199 |
| 5012R | 24 | G2 | DF | | 0-0 | 34-22-29 | D00083B | G04 | | | D41345J | 48 | | | 001-099 |
| 5012R | 24 | G2 | DF | | 0-0 | 34-22-29 | D41345J | 48 | | | D00083B | G04 | | | 115-199 |
| 5012Z | | | DF | | 0-0 | 34-22-29 | D00083B | DED | | | D41345J | | | AB | 001-099 |
| 5012Z | | | DF | | 0-0 | 34-22-29 | D41345J | | | AB | D00083B | DED | | | 115-199 |
| 5013B | 24 | G2 | DG | | 4-6 | 34-22-29 | D00083A | D04 | | | TB0203Y | C090 | BJ | | ALL |
| 5013R | 24 | G2 | DG | | 0-0 | 34-22-29 | D00083A | C04 | | | TB0203Y | C091 | BJ | | ALL |
| 5013Z | | | DG | | 0-0 | 34-22-29 | D00083A | DED | | | GD01912 | ST.. | 2 | | ALL |
| 5014B | 24 | G2 | DH | | 3-10 | 34-61-22 | D00177A | H01 | | | TB0203Y | C090 | BJ | | ALL |
| 5014R | 24 | G2 | DH | | 0-0 | 34-61-22 | D00177A | G01 | | | TB0203Y | C091 | BJ | | ALL |
| 5014Z | | | DH | | 0-0 | 34-61-22 | D00177A | DED | | | GD01912 | ST.. | 2 | | ALL |
| 5015B | 24 | G2 | DI | | 2-5 | 34-22-39 | D41679J | 22 | | | TB0203Z | 111 | BJ | | 001-099 |
| 5015B | 24 | G2 | DI | | 2-7 | 34-22-39 | D41679J | 22 | | | TB0203Z | 111 | BJ | | 115-199 |
| 5015R | 24 | G2 | DI | | 0-0 | 34-22-39 | D41679J | 21 | | | TB0203Z | 112 | BJ | | ALL |
| 5015Z | | | DI | | 0-0 | 34-22-39 | D41679J | 20 | | | GD01915 | ST.. | 2 | | 001-099 |
| 5015Z | | | DI | | 0-0 | 34-22-39 | D41679J | 20 | | | GD01914 | ST.. | 2 | | 115-199 |
| 5017B | 24 | G2 | DK | | 6-0 | 34-12-22 | D00291B | B08 | | | TB0203Z | 113 | BJ | | ALL |
| 5017R | 24 | G2 | DK | | 0-0 | 34-12-22 | D00291B | A08 | | | TB0203Z | 114 | BJ | | ALL |
| 5017Z | | | DK | | 0-0 | 34-12-22 | D00291B | DED | | | GD01916 | ST.. | 2 | | ALL |
| 5018B | 24 | G2 | DL | | 3-6 | 34-53-21 | D41345J | 25 | | | TB0203Z | 113 | BJ | | 001-099 |
| 5018B | 24 | G2 | DL | | 3-7 | 34-53-21 | D41345J | 25 | | | TB0203Z | 113 | BJ | | 115-199 |
| 5018R | 24 | G2 | DL | | 0-0 | 34-53-21 | D41345J | 24 | | | TB0203Z | 114 | BJ | | ALL |
| 5018Z | | | DL | | 0-0 | 34-53-21 | D41345J | 26 | | | GD01916 | ST.. | 2 | | ALL |
| 5019B | 24 | G2 | DM | | 3-6 | 34-53-11 | D41345J | 22 | | | TB0203Z | 111 | BJ | | 001-099 |
| 5019B | 24 | G2 | DM | | 3-7 | 34-53-11 | D41345J | 22 | | | TB0203Z | 111 | BJ | | 115-199 |
| 5019R | 24 | G2 | DM | | 0-0 | 34-53-11 | D41345J | 21 | | | TB0203Z | 112 | BJ | | ALL |
| 5019Z | | | DM | | 0-0 | 34-53-11 | D41345J | 23 | | | GD01915 | ST.. | 2 | | 001-099 |
| 5019Z | | | DM | | 0-0 | 34-53-11 | D41345J | 23 | | | GD01916 | ST.. | 2 | | 115-199 |
| 5020B | 24 | G2 | DN | | 3-6 | 31-41-22 | D41345J | 3 | | | TB0203Z | 111 | BJ | | 001-099 |
| 5020B | 24 | G2 | DN | | 3-7 | 31-41-22 | D41345J | 3 | | | TB0203Z | 111 | BJ | | 115-199 |
| 5020R | 24 | G2 | DN | | 0-0 | 31-41-22 | D41345J | 2 | | | TB0203Z | 112 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 80

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5029B | 24 | G2 | DW | | 2-6 | 34-22-39 | D41679J | 16 | | | TB0203Y | C096 | BJ | | 115-199 |
| 5029R | 24 | G2 | DW | | 0-0 | 34-22-39 | D41679J | 15 | | | TB0203Z | 97 | BJ | | 001-099 |
| 5029R | 24 | G2 | DW | | 0-0 | 34-22-39 | D41679J | 15 | | | TB0203Y | C097 | BJ | | 115-199 |
| 5029Z | | | DW | | 0-0 | 34-22-39 | D41679J | 14 | | | GD01913 | ST.. | 2 | | ALL |
| 5030B | 24 | G2 | DX | | 4-6 | 34-22-28 | D00083B | B05 | | | TB0203Y | A094 | BJ | | ALL |
| 5030R | 24 | G2 | DX | | 0-0 | 34-22-28 | D00083B | A05 | | | TB0203Y | A095 | BJ | | ALL |
| 5030Z | | | DX | | 0-0 | 34-22-28 | D00083B | DED | | | GD01913 | ST.. | 2 | | ALL |
| 5031B | 24 | G2 | DY | | 2-7 | 34-22-28 | D41393J | 2 | | | TB0203Y | A094 | BJ | | 001-099 |
| 5031B | 24 | G2 | DY | | 2-3 | 34-22-28 | D41393J | 2 | | | TB0203Y | A094 | BJ | | 115-199 |
| 5031R | 24 | G2 | DY | | 0-0 | 34-22-28 | D41393J | 1 | | | TB0203Y | A095 | BJ | | ALL |
| 5031Z | | | DY | | 0-0 | 34-22-28 | D41393J | 3 | | | GD01913 | ST.. | 2 | | ALL |
| 5032B | 24 | G2 | DZ | | 3-1 | 34-43-11 | D41063J | 5 | | | TB0203Y | A094 | BJ | | 001-099 |
| 5032B | 24 | G2 | DZ | | 3-5 | 34-43-11 | D41063J | 5 | | | TB0203Y | A094 | BJ | | 115-199 |
| 5032R | 24 | G2 | DZ | | 0-0 | 34-43-11 | D41063J | 4 | | | TB0203Y | A095 | BJ | | ALL |
| 5032Z | | | DZ | | 0-0 | 34-43-11 | D41063J | 6 | | | GD01913 | ST.. | 2 | | ALL |
| 5033B | 24 | G2 | EA | | 3-4 | 34-61-11 | D00177A | H13 | | | D41565J | 2 | | | 001-099 |
| 5033B | 24 | G2 | EA | | 3-5 | 34-61-11 | D41565J | 2 | | | D00177A | H13 | | | 115-199 |
| 5033R | 24 | G2 | EA | | 0-0 | 34-61-11 | D00177A | G13 | | | D41565J | 3 | | | 001-099 |
| 5033R | 24 | G2 | EA | | 0-0 | 34-61-11 | D41565J | 3 | | | D00177A | G13 | | | 115-199 |
| 5033Z | | | EA | | 0-0 | 34-61-11 | D00177A | DED | | | D41565J | | | AC | 001-099 |
| 5033Z | | | EA | | 0-0 | 34-61-11 | D41565J | | | AC | D00177A | DED | | | 115-199 |
| 5034B | 24 | G2 | EB | | 3-4 | 34-61-11 | D00177A | E11 | | | D41565J | 5 | | | 001-099 |
| 5034B | 24 | G2 | EB | | 3-5 | 34-61-11 | D41565J | 5 | | | D00177A | E11 | | | 115-199 |
| 5034R | 24 | G2 | EB | | 0-0 | 34-61-11 | D00177A | D11 | | | D41565J | 6 | | | 001-099 |
| 5034R | 24 | G2 | EB | | 0-0 | 34-61-11 | D41565J | 6 | | | D00177A | D11 | | | 115-199 |
| 5034Z | | | EB | | 0-0 | 34-61-11 | D00177A | DED | | | D41565J | | | AD | 001-099 |
| 5034Z | | | EB | | 0-0 | 34-61-11 | D41565J | | | AD | D00177A | DED | | | 115-199 |
| 5035B | 24 | G2 | EC | | 3-4 | 34-61-11 | D00177B | H01 | | | D41565J | 10 | | | 001-099 |
| 5035B | 24 | G2 | EC | | 3-5 | 34-61-11 | D41565J | 10 | | | D00177B | H01 | | | 115-199 |
| 5035R | 24 | G2 | EC | | 0-0 | 34-61-11 | D00177B | G01 | | | D41565J | 9 | | | 001-099 |
| 5035R | 24 | G2 | EC | | 0-0 | 34-61-11 | D41565J | 9 | | | D00177B | G01 | | | 115-199 |
| 5035Z | | | EC | | 0-0 | 34-61-11 | D00177B | DED | | | D41565J | | | AE | 001-099 |
| 5035Z | | | EC | | 0-0 | 34-61-11 | D41565J | | | AE | D00177B | DED | | | 115-199 |
| 5036B | 24 | G2 | ED | | 3-8 | 34-51-21 | D42087J | 5 | | | TB0203Y | A073 | BJ | | ALL |
| 5036R | 24 | G2 | ED | | 0-0 | 34-51-21 | D42087J | 4 | | | TB0203Y | A074 | BJ | | ALL |
| 5036Z | | | ED | | 0-0 | 34-51-21 | D42087J | 6 | | | GD01910 | ST.. | 2 | | ALL |
| 5037B | 24 | G2 | EE | | 2-11 | 34-61-13 | D41603J | 6 | | | TB0203Y | A073 | BJ | | ALL |
| 5037R | 24 | G2 | EE | | 0-0 | 34-61-13 | D41603J | 5 | | | TB0203Y | A074 | BJ | | ALL |
| 5037Z | | | EE | | 0-0 | 34-61-13 | D41603J | 7 | | | GD01910 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 82

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | |
| 5038B | 24 | G2 | EF | | 3-3 | 34-61-22 | D00177B | E01 | | | TB0203Y | A073 | BJ | | ALL |
| 5038R | 24 | G2 | EF | | 0-0 | 34-61-22 | D00177B | D01 | | | TB0203Y | A074 | BJ | | ALL |
| 5038Z | | | EF | | 0-0 | 34-61-22 | D00177B | DED | | | GD01910 | ST.. | 2 | | ALL |
| 5039B | 24 | G2 | EG | | 2-7 | 34-61-13 | D41345J | 5 | | | TB0203Y | C073 | BJ | | 001-099 |
| 5039B | 24 | G2 | EG | | 2-8 | 34-61-13 | D41345J | 5 | | | TB0203Y | C073 | BJ | | 115-199 |
| 5039R | 24 | G2 | EG | | 0-0 | 34-61-13 | D41345J | 4 | | | TB0203Y | C074 | BJ | | ALL |
| 5039Z | | | EG | | 0-0 | 34-61-13 | D41345J | 6 | | | GD01910 | ST.. | 2 | | ALL |
| 5040B | 24 | G2 | EH | | 2-11 | 34-61-13 | D41603J | 9 | | | TB0203Y | C073 | BJ | | ALL |
| 5040R | 24 | G2 | EH | | 0-0 | 34-61-13 | D41603J | 8 | | | TB0203Y | C074 | BJ | | ALL |
| 5040Z | | | EH | | 0-0 | 34-61-13 | D41603J | 10 | | | GD01910 | ST.. | 2 | | ALL |
| 5041B | 24 | G2 | EI | | 3-3 | 34-61-22 | D00177B | H07 | | | TB0203Y | C073 | BJ | | ALL |
| 5041R | 24 | G2 | EI | | 0-0 | 34-61-22 | D00177B | G07 | | | TB0203Y | C074 | BJ | | ALL |
| 5041Z | | | EI | | 0-0 | 34-61-22 | D00177B | DED | | | GD01910 | ST.. | 2 | | ALL |
| 5042B | 24 | G2 | EJ | | 2-7 | 34-61-13 | D41603J | 16 | | | TB0203Y | A063 | BJ | | ALL |
| 5042R | 24 | G2 | EJ | | 0-0 | 34-61-13 | D41603J | 15 | | | TB0203Y | A064 | BJ | | ALL |
| 5042Z | | | EJ | | 0-0 | 34-61-13 | D41603J | 17 | | | GD01909 | ST.. | 2 | | ALL |
| 5043B | 24 | G2 | EK | | 3-3 | 34-61-22 | D41881J | 11 | | | TB0203Y | A063 | BJ | | 001-099 |
| 5043B | 24 | G2 | EK | | 2-10 | 34-61-22 | D41881J | 11 | | | TB0203Y | A063 | BJ | | 115-199 |
| 5043R | 24 | G2 | EK | | 0-0 | 34-61-22 | D41881J | 10 | | | TB0203Y | A064 | BJ | | ALL |
| 5043Z | | | EK | | 0-0 | 34-61-22 | D41881J | 12 | | | GD01909 | ST.. | 2 | | ALL |
| 5044B | 24 | G2 | EL | | 2-11 | 34-61-22 | D00177B | B03 | | | TB0203Y | A063 | BJ | | ALL |
| 5044R | 24 | G2 | EL | | 0-0 | 34-61-22 | D00177B | A03 | | | TB0203Y | A064 | BJ | | ALL |
| 5044Z | | | EL | | 0-0 | 34-61-22 | D00177B | DED | | | GD01909 | ST.. | 2 | | ALL |
| 5045B | 24 | G2 | EM | | 4-6 | 34-22-29 | D00083A | K05 | | | TB0203Y | C094 | BJ | | ALL |
| 5045R | 24 | G2 | EM | | 0-0 | 34-22-29 | D00083A | J05 | | | TB0203Y | C095 | BJ | | ALL |
| 5045Z | | | EM | | 0-0 | 34-22-29 | D00083A | DED | | | GD01913 | ST.. | 2 | | ALL |
| 5046B | 24 | G2 | EN | | 3-10 | 34-61-22 | D00177A | H05 | | | TB0203Y | C094 | BJ | | ALL |
| 5046R | 24 | G2 | EN | | 0-0 | 34-61-22 | D00177A | G05 | | | TB0203Y | C095 | BJ | | ALL |
| 5046Z | | | EN | | 0-0 | 34-61-22 | D00177A | DED | | | GD01913 | ST.. | 2 | | ALL |
| 5047B | 24 | G2 | EO | | 3-0 | 34-61-22 | D00177A | E15 | | | D41603J | 29 | | | 001-099 |
| 5047B | 24 | G2 | EO | | 3-0 | 34-61-22 | D41603J | 29 | | | D00177A | E15 | | | 115-199 |
| 5047R | 24 | G2 | EO | | 0-0 | 34-61-22 | D00177A | D15 | | | D41603J | 28 | | | 001-099 |
| 5047R | 24 | G2 | EO | | 0-0 | 34-61-22 | D41603J | 28 | | | D00177A | D15 | | | 115-199 |
| 5047Z | | | EO | | 0-0 | 34-61-22 | D00177A | DED | | | D41603J | | | | 001-099 |
| 5047Z | | | EO | | 0-0 | 34-61-22 | D41603J | | AF | | D00177A | DED | | AF | 115-199 |
| 5048B | 24 | G2 | EP | | 3-9 | 34-61-13 | D41603J | 13 | | | TB0203Z | 113 | BJ | | ALL |
| 5048R | 24 | G2 | EP | | 0-0 | 34-61-13 | D41603J | 12 | | | TB0203Z | 114 | BJ | | ALL |
| 5048Z | | | EP | | 0-0 | 34-61-13 | D41603J | 14 | | | GD01916 | ST.. | 2 | | 001-099 |
| 5048Z | | | EP | | 0-0 | 34-61-13 | D41603J | 14 | | | GD01914 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 83

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5049B | 24 | G2 | EQ | | 4-2 | 34-61-22 | D00177B | E05 | | | TB0203Z | 113 | BJ | | ALL |
| 5049R | 24 | G2 | EQ | | 0-0 | 34-61-22 | D00177B | D05 | | | TB0203Z | 114 | BJ | | ALL |
| 5049Z | | | EQ | | 0-0 | 34-61-22 | D00177B | DED | | | GD01916 | ST.. | 2 | | 001-099 |
| 5049Z | | | EQ | | 0-0 | 34-61-22 | D00177B | DED | | | GD01914 | ST.. | 2 | | 115-199 |
| 5051B | 24 | G2 | ES | | 3-3 | 34-61-24 | D00177A | H07 | | | TB0203Y | C077 | BJ | | ALL |
| 5051R | 24 | G2 | ES | | 0-0 | 34-61-24 | D00177A | G07 | | | TB0203Y | C078 | BJ | | ALL |
| 5051Z | | | ES | | 0-0 | 34-61-24 | D00177A | DED | | | GD01911 | ST.. | 2 | | ALL |
| 5052B | 24 | G2 | ET | | 3-10 | 22-13-21 | D42085J | 29 | | | TB0203Y | C077 | BJ | | ALL |
| 5052R | 24 | G2 | ET | | 0-0 | 22-13-21 | D42085J | 28 | | | TB0203Y | C078 | BJ | | ALL |
| 5052Z | | | ET | | 0-0 | 22-13-21 | D42085J | 30 | | | GD01910 | ST.. | 2 | | ALL |
| 5053B | 24 | G2 | EU | | 3-7 | 22-13-21 | D00075A | B09 | | | TB0203Y | C077 | BJ | | ALL |
| 5053R | 24 | G2 | EU | | 0-0 | 22-13-21 | D00075A | A09 | | | TB0203Y | C078 | BJ | | ALL |
| 5053Z | | | EU | | 0-0 | 22-13-21 | D00075A | DED | | | GD01911 | ST.. | 2 | | ALL |
| 5054B | 24 | G2 | EV | | 3-4 | 34-61-24 | D41345J | 8 | | | TB0203Y | C030 | BJ | | 001-099 |
| 5054B | 24 | G2 | EV | | 3-5 | 34-61-24 | D41345J | 8 | | | TB0203Y | C030 | BJ | | 115-199 |
| 5054R | 24 | G2 | EV | | 0-0 | 34-61-24 | D41345J | 7 | | | TB0203Y | A030 | BJ | | ALL |
| 5054Z | | | EV | | 0-0 | 34-61-24 | D41345J | 9 | | | GD01904 | ST.. | 2 | | ALL |
| 5055B | 24 | G2 | EW | | 3-4 | 34-61-24 | D00177A | E05 | | | D41345J | 12 | | | 001-099 |
| 5055B | 24 | G2 | EW | | 3-6 | 34-61-24 | D41345J | 12 | | | D00177A | E05 | | | 115-199 |
| 5055R | 24 | G2 | EW | | 0-0 | 34-61-24 | D00177A | D05 | | | D41345J | 11 | | | 001-099 |
| 5055R | 24 | G2 | EW | | 0-0 | 34-61-24 | D41345J | 11 | | | D00177A | D05 | | | 115-199 |
| 5055Z | | | EW | | 0-0 | 34-61-24 | D00177A | DED | | | D41345J | | | AH | 001-099 |
| 5055Z | | | EW | | 0-0 | 34-61-24 | D41345J | | AH | | D00177A | DED | | | 115-199 |
| 5058B | 24 | G2 | EZ | | 3-7 | 22-12-21 | D00075A | D09 | | | TB0203Z | 82 | BJ | | ALL |
| 5058R | 24 | G2 | EZ | | 0-0 | 22-12-21 | D00075A | C09 | | | TB0203Z | 83 | BJ | | ALL |
| 5058Z | | | EZ | | 0-0 | 22-12-21 | D00075A | DED | | | GD01910 | ST.. | 2 | | ALL |
| 5059B | 24 | G2 | FA | | 3-4 | 34-61-25 | D00177A | H09 | | | TB0203Z | 82 | BJ | | ALL |
| 5059R | 24 | G2 | FA | | 0-0 | 34-61-25 | D00177A | G09 | | | TB0203Z | 83 | BJ | | ALL |
| 5059Z | | | FA | | 0-0 | 34-61-25 | D00177A | DED | | | GD01910 | ST.. | 2 | | ALL |
| 5060B | 24 | G2 | FB | | 3-10 | 22-32-11 | D41821J | 5 | | | TB0203Z | 82 | BJ | | ALL |
| 5060R | 24 | G2 | FB | | 0-0 | 22-32-11 | D41821J | 4 | | | TB0203Z | 83 | BJ | | ALL |
| 5060Z | | | FB | | 0-0 | 22-32-11 | D41821J | 6 | | | GD01910 | ST.. | 2 | | ALL |
| 5061B | 24 | G2 | FC | | 2-10 | 34-21-21 | D41881J | 5 | | | TB0203Z | 82 | BJ | | 001-099 |
| 5061B | 24 | G2 | FC | | 2-6 | 34-21-21 | D41881J | 5 | | | TB0203Z | 82 | BJ | | 115-199 |
| 5061R | 24 | G2 | FC | | 0-0 | 34-21-21 | D41881J | 4 | | | TB0203Z | 83 | BJ | | ALL |
| 5061Z | | | FC | | 0-0 | 34-21-21 | D41881J | 6 | | | GD01910 | ST.. | 2 | | ALL |
| 5062B | 24 | G2 | FD | | 6-0 | 34-12-22 | D00291B | B02 | | | TB0203Z | 119 | BJ | | ALL |
| 5062R | 24 | G2 | FD | | 0-0 | 34-12-22 | D00291B | A02 | | | TB0203Z | 120 | BJ | | ALL |
| 5062Z | | | FD | | 0-0 | 34-12-22 | D00291B | DED | | | GD01916 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 84

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5064B | 24 | G2 | FF | | 4-4 | 22-32-11 | D41821J | | 2 | | TB0203Z | 105 | BJ | | ALL |
| 5064R | 24 | G2 | FF | | 0-0 | 22-32-11 | D41821J | | 1 | | TB0203Z | 106 | BJ | | ALL |
| 5064Z | | | FF | | 0-0 | 22-32-11 | D41821J | | 3 | | GD01914 | ST.. | 2 | | ALL |
| 5065B | 24 | G2 | FG | | 3-6 | 22-24-21 | D41345J | | 40 | | TB0203Z | 119 | BJ | | 001-099 |
| 5065B | 24 | G2 | FG | | 3-7 | 22-24-21 | D41345J | | 40 | | TB0203Z | 119 | BJ | | 115-199 |
| 5065R | 24 | G2 | FG | | 0-0 | 22-24-21 | D41345J | | 39 | | TB0203Z | 120 | BJ | | ALL |
| 5065Z | | | FG | | 0-0 | 22-24-21 | D41345J | | 41 | | GD01916 | ST.. | 2 | | ALL |
| 5066B | 22 | GU | FH | | 2-9 | 34-12-21 | D00291B | | J08 | | D42133J | 3 | | | 001-099 |
| 5066B | 22 | GU | FH | | 2-9 | 34-12-21 | D42133J | | 3 | | D00291B | J08 | | | 115-199 |
| 5066R | 22 | GU | FH | | 0-0 | 34-12-21 | D00291B | | H08 | | D42133J | 2 | | | 001-099 |
| 5066R | 22 | GU | FH | | 0-0 | 34-12-21 | D42133J | | 2 | | D00291B | H08 | | | 115-199 |
| 5066Z | | | FH | | 0-0 | 34-12-21 | D00291B | | K08 | | D42133J | 4 | | | 001-099 |
| 5066Z | | | FH | | 0-0 | 34-12-21 | D42133J | | 4 | | D00291B | K08 | | | 115-199 |
| 5067B | 24 | G2 | FI | | 4-7 | 34-13-21 | D42087J | | 3 | | TB0203Z | 109 | BJ | | ALL |
| 5067R | 24 | G2 | FI | | 0-0 | 34-13-21 | D42087J | | 2 | | TB0203Z | 110 | BJ | | ALL |
| 5067Z | | | FI | | 0-0 | 34-13-21 | D42087J | | 1 | | GD01915 | ST.. | 2 | | ALL |
| 5068B | 24 | G2 | FJ | | 2-8 | 34-31-21 | D42107J | | 3 | | TB0203Y | A047 | BJ | | 001-099 |
| 5068B | 24 | G2 | FJ | | 3-0 | 34-31-21 | D42107J | | 13 | | TB0203Y | A047 | BJ | | 115-199 |
| 5068R | 24 | G2 | FJ | | 0-0 | 34-31-21 | D42107J | | 4 | | TB0203Y | A048 | BJ | | 001-099 |
| 5068R | 24 | G2 | FJ | | 0-0 | 34-31-21 | D42107J | | 14 | | TB0203Y | A048 | BJ | | 115-199 |
| 5068Z | | | FJ | | 0-0 | 34-31-21 | D42107J | | 2 | | GD01907 | ST.. | 2 | | 001-099 |
| 5068Z | | | FJ | | 0-0 | 34-31-21 | D42107J | | 12 | | GD01907 | ST.. | 2 | | 115-199 |
| 5069B | 24 | G2 | FK | | 3-6 | 34-31-21 | D00205B | | C13 | | TB0203Y | A047 | BJ | | 001-099 |
| 5069B | 24 | G2 | FK | | 3-6 | 34-31-21 | D02941B | | K01 | | TB0203Y | A047 | BJ | | 115-199 |
| 5069R | 24 | G2 | FK | | 0-0 | 34-31-21 | D00205B | | B13 | | TB0203Y | A048 | BJ | | 001-099 |
| 5069R | 24 | G2 | FK | | 0-0 | 34-31-21 | D02941B | | J01 | | TB0203Y | A048 | BJ | | 115-199 |
| 5069Z | | | FK | | 0-0 | 34-31-21 | D00205B | | DED | | GD01907 | ST.. | 2 | | 001-099 |
| 5069Z | | | FK | | 0-0 | 34-31-21 | D02941B | | DED | | GD01907 | ST.. | 2 | | 115-199 |
| 5070B | 24 | G2 | FL | | 2-11 | 34-31-21 | D42087J | | 22 | | TB0203Y | A047 | BJ | | ALL |
| 5070R | 24 | G2 | FL | | 0-0 | 34-31-21 | D42087J | | 21 | | TB0203Y | A048 | BJ | | ALL |
| 5070Z | | | FL | | 0-0 | 34-31-21 | D42087J | | 23 | | GD01907 | ST.. | 2 | | ALL |
| 5071B | 24 | G2 | FM | | 2-11 | 34-55-21 | D41347J | | 34 | | TB0203Y | A042 | BJ | | 001-099 |
| 5071B | 24 | G2 | FM | | 2-10 | 34-55-21 | D41347J | | 34 | | TB0203Y | A042 | BJ | | 115-199 |
| 5071R | 24 | G2 | FM | | 0-0 | 34-55-21 | D41347J | | 33 | | TB0203Y | A041 | BJ | | ALL |
| 5071Z | | | FM | | 0-0 | 34-55-21 | D41347J | | 35 | | GD01906 | ST.. | 2 | | ALL |
| 5072B | 24 | G2 | FN | | 3-9 | 34-61-25 | D41347J | | 41 | | TB0203Z | 79 | BJ | | 001-099 |
| 5072B | 24 | G2 | FN | | 3-8 | 34-61-25 | D41347J | | 41 | | TB0203Z | 79 | BJ | | 115-199 |
| 5072R | 24 | G2 | FN | | 0-0 | 34-61-25 | D41347J | | 40 | | TB0203Z | 80 | BJ | | ALL |
| 5072Z | | | FN | | 0-0 | 34-61-25 | D41347J | | 42 | | GD01911 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 85

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5073B | 24 | G2 | FO | | 2-7 | 34-61-25 | D41345J | 15 | | | TB0203Z | 79 | BJ | | 001-099 |
| 5073B | 24 | G2 | FO | | 2-8 | 34-61-25 | D41345J | 15 | | | TB0203Z | 79 | BJ | | 115-199 |
| 5073R | 24 | G2 | FO | | 0-0 | 34-61-25 | D41345J | 14 | | | TB0203Z | 80 | BJ | | ALL |
| 5073Z | | | FO | | 0-0 | 34-61-25 | D41345J | 16 | | | GD01911 | ST.. | 2 | | ALL |
| 5074B | 24 | G2 | FP | | 3-3 | 34-61-25 | D00177B | E07 | | | TB0203Z | 79 | BJ | | ALL |
| 5074R | 24 | G2 | FP | | 0-0 | 34-61-25 | D00177B | D07 | | | TB0203Z | 80 | BJ | | ALL |
| 5074Z | | | FP | | 0-0 | 34-61-25 | D00177B | DED | | | GD01911 | ST.. | 2 | | ALL |
| 5075B | 24 | G2 | HR | | 4-6 | 22-12-31 | D00083B | B01 | | | TB0203Y | C092 | BJ | | 001-099 |
| 5075B | 24 | G2 | HR | | 4-6 | 22-12-31 | TB0203Y | C092 | BJ | | D00083B | B01 | | | 115-199 |
| 5075R | 24 | G2 | HR | | 0-0 | 22-12-31 | D00083B | A01 | | | TB0203Y | C093 | BJ | | 001-099 |
| 5075R | 24 | G2 | HR | | 0-0 | 22-12-31 | TB0203Y | C093 | BJ | | D00083B | A01 | | | 115-199 |
| 5075Z | | | HR | | 0-0 | 22-12-31 | D00083B | DED | | | GD01913 | ST.. | 2 | | 001-099 |
| 5075Z | | | HR | | 0-0 | 22-12-31 | GD01913 | ST.. | 2 | | D00083B | DED | | | 115-199 |
| 5076B | 24 | G2 | HS | | 3-6 | 22-13-21 | D00205B | C07 | | | TB0203Y | A045 | BJ | | 001-099 |
| 5076B | 24 | G2 | HS | | 3-6 | 22-13-21 | TB0203Y | A045 | BJ | | D02941B | B01 | | | 115-199 |
| 5076R | 24 | G2 | HS | | 0-0 | 22-13-21 | D00205B | B07 | | | TB0203Y | A046 | BJ | | 001-099 |
| 5076R | 24 | G2 | HS | | 0-0 | 22-13-21 | TB0203Y | A046 | BJ | | D02941B | A01 | | | 115-199 |
| 5076Z | | | HS | | 0-0 | 22-13-21 | D00205B | DED | | | GD01907 | ST.. | 2 | | 001-099 |
| 5076Z | | | HS | | 0-0 | 22-13-21 | GD01907 | ST.. | 2 | | D02941B | DED | | | 115-199 |
| 5077B | 24 | G2 | FS | | 3-9 | 22-41-11 | D41347J | 44 | | | TB0203Z | 79 | BJ | | 001-099 |
| 5077B | 24 | G2 | FS | | 3-8 | 22-41-11 | D41347J | 44 | | | TB0203Z | 79 | BJ | | 115-199 |
| 5077R | 24 | G2 | FS | | 0-0 | 22-41-11 | D41347J | 43 | | | TB0203Z | 80 | BJ | | ALL |
| 5077Z | | | FS | | 0-0 | 22-41-11 | D41347J | 45 | | | GD01911 | ST.. | 2 | | ALL |
| 5078B | 24 | G2 | FT | | 2-6 | SPARE | D41881J | 16 | | | TB0203Z | 105 | BJ | | 001-099 |
| 5078B | 24 | G2 | FT | | 2-2 | SPARE | D41881J | 16 | | | TB0203Z | 105 | BJ | | 115-199 |
| 5078R | 24 | G2 | FT | | 0-0 | SPARE | D41881J | 17 | | | TB0203Z | 106 | BJ | | ALL |
| 5078Z | | | FT | | 0-0 | SPARE | D41881J | 18 | | | GD01914 | ST.. | 2 | | 001-099 |
| 5078Z | | | FT | | 0-0 | SPARE | D41881J | 18 | | | GD01916 | ST.. | 2 | | 115-199 |
| 5079B | 24 | G2 | FU | | 3-2 | 34-43-11 | D41679J | 2 | | | D41063J | 8 | | | 001-099 |
| 5079B | 24 | G2 | FU | | 3-9 | 34-43-11 | D41679J | 2 | | | D41063J | 8 | | | 115-199 |
| 5079R | 24 | G2 | FU | | 0-0 | 34-43-11 | D41679J | 3 | | | D41063J | 7 | | | ALL |
| 5079Z | | | FU | | 0-0 | 34-43-11 | D41679J | 1 | | | D41063J | 9 | | | ALL |
| 5080B | 24 | 7K | FV | | 3-11 | 34-43-11 | D41679J | 5 | | | TB0204Y | A001 | BJ | | 001, 003-099 |
| 5080B | 24 | 7K | FV | | 4-2 | 34-43-11 | D41679J | 5 | | | TB0204Y | A001 | BJ | | 115-199 |
| 5080W | 24 | 7K | FV | | 0-0 | 34-43-11 | D41679J | 6 | | | TB0204Y | A002 | BJ | | 001, 003-099, 115-199 |
| 5080Z | | | FV | | 0-0 | 34-43-11 | D41679J | 4 | | | GD01917 | ST.. | 2 | | 001, 003-099, 115-199 |
| 5081B | 24 | 7K | FW | | 3-3 | 34-43-11 | D41063J | 2 | | | TB0204Y | A001 | BJ | | 001, 003-099 |
| 5081B | 24 | 7K | FW | | 3-7 | 34-43-11 | D41063J | 2 | | | TB0204Y | A001 | BJ | | 115-199 |
| 5081W | 24 | 7K | FW | | 0-0 | 34-43-11 | D41063J | 1 | | | TB0204Y | A002 | BJ | | 001, 003-099, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 86

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5081Z | | | | FW | 0-0 | 34-43-11 | D41063J | 3 | | | GD01917 | ST.. | 2 | | 001, 003-099, 115-199 |
| 5082B | 24 | 7K | | FX | 0-6 | 34-43-11 | D00083A | F03 | | | TB0204Y | A001 | BJ | | 001, 003-099, 115-199 |
| 5082W | 24 | 7K | | FX | 0-0 | 34-43-11 | D00083A | E03 | | | TB0204Y | A002 | BJ | | 001, 003-099, 115-199 |
| 5082Z | | | | FX | 0-0 | 34-43-11 | D00083A | DED | | | GD01917 | ST.. | 2 | | 001, 003-099, 115-199 |
| 5085B | 24 | G2 | | GA | 4-6 | 22-12-11 | D00083A | B01 | | | TB0203Y | A092 | BJ | | ALL |
| 5085R | 24 | G2 | | GA | 0-0 | 22-12-11 | D00083A | A01 | | | TB0203Y | A093 | BJ | | ALL |
| 5085Z | | | | GA | 0-0 | 22-12-11 | D00083A | DED | | | GD01913 | ST.. | 2 | | ALL |
| 5086B | 24 | G2 | | GB | 3-2 | 22-12-11 | D41565J | 43 | | | TB0203Y | A092 | BJ | | ALL |
| 5086R | 24 | G2 | | GB | 0-0 | 22-12-11 | D41565J | 42 | | | TB0203Y | A093 | BJ | | ALL |
| 5086Z | | | | GB | 0-0 | 22-12-11 | D41565J | 44 | | | GD01913 | ST.. | 2 | | ALL |
| 5087B | 24 | G2 | | GC | 4-11 | 22-12-21 | D00075B | B02 | | | TB0203Y | A026 | BJ | | ALL |
| 5087R | 24 | G2 | | GC | 0-0 | 22-12-21 | D00075B | B01 | | | TB0203Y | A027 | BJ | | ALL |
| 5087Z | | | | GC | 0-0 | 22-12-21 | D00075B | DED | | | GD01904 | ST.. | 2 | | ALL |
| 5088B | 24 | G2 | | GD | 3-11 | 22-12-21 | D41679J | 45 | | | TB0203Y | A026 | BJ | | 001-099 |
| 5088B | 24 | G2 | | GD | 4-1 | 22-12-21 | D41679J | 45 | | | TB0203Y | A026 | BJ | | 115-199 |
| 5088R | 24 | G2 | | GD | 0-0 | 22-12-21 | D41679J | 44 | | | TB0203Y | A027 | BJ | | ALL |
| 5088Z | | | | GD | 0-0 | 22-12-21 | D41679J | 46 | | | GD01904 | ST.. | 2 | | ALL |
| 5089B | 24 | G2 | | GE | 2-8 | 22-12-21 | D00083D | B01 | | | TB0203Y | A026 | BJ | | ALL |
| 5089R | 24 | G2 | | GE | 0-0 | 22-12-21 | D00083D | A01 | | | TB0203Y | A027 | BJ | | ALL |
| 5089Z | | | | GE | 0-0 | 22-12-21 | D00083D | DED | | | GD01905 | ST.. | 2 | | ALL |
| 5090B | 24 | G2 | | GF | 3-11 | 22-12-21 | D41679J | 47 | | | TB0203Y | A026 | BJ | | 001-099 |
| 5090B | 24 | G2 | | GF | 4-1 | 22-12-21 | D41679J | 47 | | | TB0203Y | A026 | BJ | | 115-199 |
| 5090R | 24 | G2 | | GF | 0-0 | 22-12-21 | D41679J | 48 | | | TB0203Y | A027 | BJ | | ALL |
| 5090Z | | | | GF | 0-0 | 22-12-21 | D41679J | 49 | | | GD01904 | ST.. | 2 | | ALL |
| 5091B | 24 | G2 | | GG | 2-8 | 22-12-21 | D42085J | 26 | | | TB0203Y | C026 | BJ | | ALL |
| 5091R | 24 | G2 | | GG | 0-0 | 22-12-21 | D42085J | 25 | | | TB0203Y | C027 | BJ | | ALL |
| 5091Z | | | | GG | 0-0 | 22-12-21 | D42085J | 27 | | | GD01904 | ST.. | 2 | | ALL |
| 5092B | 24 | G2 | | GH | 4-11 | 22-12-21 | D00075B | B04 | | | TB0203Y | C026 | BJ | | ALL |
| 5092R | 24 | G2 | | GH | 0-0 | 22-12-21 | D00075B | B03 | | | TB0203Y | C027 | BJ | | ALL |
| 5092Z | | | | GH | 0-0 | 22-12-21 | D00075B | DED | | | GD01904 | ST.. | 2 | | ALL |
| 5093B | 24 | G2 | | GI | 6-0 | 22-12-21 | D00075B | C02 | | | D41347J | 6 | | | 001-099 |
| 5093B | 24 | G2 | | GI | 5-5 | 22-12-21 | D41347J | 6 | | | D00075B | C02 | | | 115-199 |
| 5093R | 24 | G2 | | GI | 0-0 | 22-12-21 | D00075B | C01 | | | D41347J | 5 | | | 001-099 |
| 5093R | 24 | G2 | | GI | 0-0 | 22-12-21 | D41347J | 5 | | | D00075B | C01 | | | 115-199 |
| 5093Z | | | | GI | 0-0 | 22-12-21 | D00075B | DED | | | D41347J | | | AO | 001-099 |
| 5093Z | | | | GI | 0-0 | 22-12-21 | D41347J | | AO | | D00075B | DED | | | 115-199 |
| 5094B | 24 | G2 | | GJ | 2-7 | 22-12-31 | D41393J | 8 | | | TB0203Y | C092 | BJ | | 001-099 |
| 5094B | 24 | G2 | | GJ | 2-3 | 22-12-31 | D41393J | 8 | | | TB0203Y | C092 | BJ | | 115-199 |
| 5094R | 24 | G2 | | GJ | 0-0 | 22-12-31 | D41393J | 7 | | | TB0203Y | C093 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 87

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5094Z | | | | GJ | 0-0 | 22-12-31 | D41393J | 9 | | | GD01913 | ST.. | 2 | | ALL |
| 5095B | 24 | G2 | GK | | 3-4 | 22-22-21 | D41345J | 32 | | | TB0203Y | C026 | BJ | | 001-099 |
| 5095B | 24 | G2 | GK | | 3-5 | 22-22-21 | D41345J | 32 | | | TB0203Y | C026 | BJ | | 115-199 |
| 5095R | 24 | G2 | GK | | 0-0 | 22-22-21 | D41345J | 31 | | | TB0203Y | C027 | BJ | | ALL |
| 5095Z | | | | GK | 0-0 | 22-22-21 | D41345J | 33 | | | GD01904 | ST.. | 2 | | ALL |
| 5096B | 24 | G2 | GL | | 2-7 | 22-12-31 | D41393J | 5 | | | TB0203Y | C092 | BJ | | 001-099 |
| 5096B | 24 | G2 | GL | | 2-3 | 22-12-31 | D41393J | 5 | | | TB0203Y | C092 | BJ | | 115-199 |
| 5096R | 24 | G2 | GL | | 0-0 | 22-12-31 | D41393J | 4 | | | TB0203Y | C093 | BJ | | ALL |
| 5096Z | | | | GL | 0-0 | 22-12-31 | D41393J | 6 | | | GD01912 | ST.. | 2 | | ALL |
| 5097B | 24 | G2 | GM | | 4-5 | 22-13-21 | D00075B | A02 | | | TB0203Y | A045 | BJ | | ALL |
| 5097R | 24 | G2 | GM | | 0-0 | 22-13-21 | D00075B | A01 | | | TB0203Y | A046 | BJ | | ALL |
| 5097Z | | | | GM | 0-0 | 22-13-21 | D00075B | DED | | | GD01907 | ST.. | 2 | | ALL |
| 5098B | 24 | G2 | GN | | 3-6 | 22-13-21 | D00075B | E02 | | | D41881J | 8 | | | 001-099 |
| 5098B | 24 | G2 | GN | | 3-2 | 22-13-21 | D41881J | 8 | | | D00075B | E02 | | | 115-199 |
| 5098R | 24 | G2 | GN | | 0-0 | 22-13-21 | D00075B | E01 | | | D41881J | 7 | | | 001-099 |
| 5098R | 24 | G2 | GN | | 0-0 | 22-13-21 | D41881J | 7 | | | D00075B | E01 | | | 115-199 |
| 5098Z | | | | GN | 0-0 | 22-13-21 | D00075B | DED | | | D41881J | | | AY | 001-099 |
| 5098Z | | | | GN | 0-0 | 22-13-21 | D41881J | | | AY | D00075B | DED | | | 115-199 |
| 5099B | 24 | G2 | GO | | 3-6 | 22-15-11 | D00075A | H03 | | | D41393J | 20 | | | 001-099 |
| 5099B | 24 | G2 | GO | | 3-3 | 22-15-11 | D41393J | 20 | | | D00075A | H03 | | | 115-199 |
| 5099R | 24 | G2 | GO | | 0-0 | 22-15-11 | D00075A | G03 | | | D41393J | 19 | | | 001-099 |
| 5099R | 24 | G2 | GO | | 0-0 | 22-15-11 | D41393J | 19 | | | D00075A | G03 | | | 115-199 |
| 5099Z | | | | GO | 0-0 | 22-15-11 | D00075A | DED | | | D41393J | | | AZ | 001-099 |
| 5099Z | | | | GO | 0-0 | 22-15-11 | D41393J | | | AZ | D00075A | DED | | | 115-199 |
| 5100B | 24 | G2 | GP | | 6-0 | 22-15-11 | D00075B | F03 | | | D41347J | 24 | | | 001-099 |
| 5100B | 24 | G2 | GP | | 5-5 | 22-15-11 | D41347J | 24 | | | D00075B | F03 | | | 115-199 |
| 5100R | 24 | G2 | GP | | 0-0 | 22-15-11 | D00075B | E03 | | | D41347J | 23 | | | 001-099 |
| 5100R | 24 | G2 | GP | | 0-0 | 22-15-11 | D41347J | 23 | | | D00075B | E03 | | | 115-199 |
| 5100Z | | | | GP | 0-0 | 22-15-11 | D00075B | DED | | | D41347J | | | BA | 001-099 |
| 5100Z | | | | GP | 0-0 | 22-15-11 | D41347J | | | BA | D00075B | DED | | | 115-199 |
| 5101B | 24 | G2 | GQ | | 3-3 | 22-15-11 | D00075B | F02 | | | D41679J | 40 | | | 001-099 |
| 5101B | 24 | G2 | GQ | | 3-5 | 22-15-11 | D41679J | 40 | | | D00075B | F02 | | | 115-199 |
| 5101R | 24 | G2 | GQ | | 0-0 | 22-15-11 | D00075B | F01 | | | D41679J | 39 | | | 001-099 |
| 5101R | 24 | G2 | GQ | | 0-0 | 22-15-11 | D41679J | 39 | | | D00075B | F01 | | | 115-199 |
| 5101Z | | | | GQ | 0-0 | 22-15-11 | D00075B | DED | | | D41679J | | | BB | 001-099 |
| 5101Z | | | | GQ | 0-0 | 22-15-11 | D41679J | | | BB | D00075B | DED | | | 115-199 |
| 5102B | 24 | G2 | GR | | 3-6 | 22-15-11 | D00075A | E01 | | | D41743J | 1 | | | 001-099 |
| 5102B | 24 | G2 | GR | | 3-2 | 22-15-11 | D41743J | 1 | | | D00075A | E01 | | | 115-199 |
| 5102R | 24 | G2 | GR | | 0-0 | 22-15-11 | D00075A | D01 | | | D41743J | 2 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 88

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5102R | 24 | G2 | GR | | 0-0 | 22-15-11 | D41743J | 2 | | | D00075A | D01 | | | 115-199 |
| 5102Z | | | GR | | 0-0 | 22-15-11 | D00075A | DED | | | D41743J | | | BC | 001-099 |
| 5102Z | | | GR | | 0-0 | 22-15-11 | D41743J | | | BC | D00075A | DED | | | 115-199 |
| 5103B | 24 | G2 | HT | | 4-8 | 34-12-22 | D41347J | 19 | | | TB0203Z | 111 | BJ | | 001-099 |
| 5103B | 24 | G2 | HT | | 4-7 | 34-12-22 | D41347J | 19 | | | TB0203Z | 111 | BJ | | 115-199 |
| 5103R | 24 | G2 | HT | | 0-0 | 34-12-22 | D41347J | 18 | | | TB0203Z | 112 | BJ | | ALL |
| 5103Z | | | HT | | 0-0 | 34-12-22 | D41347J | 20 | | | GD01915 | ST.. | 2 | | ALL |
| 5104B | 24 | G2 | GT | | 3-1 | 22-41-12 | D00075A | A02 | | | D41095J | 2 | | | 001-099 |
| 5104B | 24 | G2 | GT | | 3-1 | 22-41-12 | D41095J | 2 | | | D00075A | A02 | | | 115-199 |
| 5104R | 24 | G2 | GT | | 0-0 | 22-41-12 | D00075A | A01 | | | D41095J | 3 | | | 001-099 |
| 5104R | 24 | G2 | GT | | 0-0 | 22-41-12 | D41095J | 3 | | | D00075A | A01 | | | 115-199 |
| 5104Z | | | GT | | 0-0 | 22-41-12 | D00075A | DED | | | D41095J | | | AP | 001-099 |
| 5104Z | | | GT | | 0-0 | 22-41-12 | D41095J | | | AP | D00075A | DED | | | 115-199 |
| 5105B | 24 | G2 | GU | | 3-2 | 22-12-11 | D41565J | 46 | | | TB0203Y | A092 | BJ | | ALL |
| 5105R | 24 | G2 | GU | | 0-0 | 22-12-11 | D41565J | 45 | | | TB0203Y | A093 | BJ | | ALL |
| 5105Z | | | GU | | 0-0 | 22-12-11 | D41565J | 47 | | | GD01913 | ST.. | 2 | | ALL |
| 5106B | 24 | G2 | GV | | 2-11 | 34-61-21 | D00177A | E13 | | | D41083J | 3 | | | 001-099 |
| 5106B | 24 | G2 | GV | | 2-10 | 34-61-21 | D41083J | 3 | | | D00177A | E13 | | | 115-199 |
| 5106R | 24 | G2 | GV | | 0-0 | 34-61-21 | D00177A | D13 | | | D41083J | 2 | | | 001-099 |
| 5106R | 24 | G2 | GV | | 0-0 | 34-61-21 | D41083J | 2 | | | D00177A | D13 | | | 115-199 |
| 5106Z | | | GV | | 0-0 | 34-61-21 | D00177A | DED | | | D41083J | | | AQ | 001-099 |
| 5106Z | | | GV | | 0-0 | 34-61-21 | D41083J | | | AQ | D00177A | DED | | | 115-199 |
| 5107B | 24 | G2 | GW | | 2-5 | 34-61-21 | D41083J | 6 | | | TB0203Y | C063 | BJ | | 001-099 |
| 5107B | 24 | G2 | GW | | 2-4 | 34-61-21 | D41083J | 6 | | | TB0203Y | C063 | BJ | | 115-199 |
| 5107R | 24 | G2 | GW | | 0-0 | 34-61-21 | D41083J | 5 | | | TB0203Y | C064 | BJ | | ALL |
| 5107Z | | | GW | | 0-0 | 34-61-21 | D41083J | 7 | | | GD01909 | ST.. | 2 | | ALL |
| 5108B | 24 | G2 | GX | | 2-11 | 34-61-21 | D00177A | B09 | | | TB0203Y | C063 | BJ | | ALL |
| 5108R | 24 | G2 | GX | | 0-0 | 34-61-21 | D00177A | A09 | | | TB0203Y | C064 | BJ | | ALL |
| 5108Z | | | GX | | 0-0 | 34-61-21 | D00177A | DED | | | GD01909 | ST.. | 2 | | ALL |
| 5109B | 24 | G2 | GY | | 2-5 | 34-61-21 | D41083J | 9 | | | D41603J | 18 | | | 001-099 |
| 5109B | 24 | G2 | GY | | 2-4 | 34-61-21 | D41083J | 9 | | | D41603J | 18 | | | 115-199 |
| 5109R | 24 | G2 | GY | | 0-0 | 34-61-21 | D41083J | 8 | | | D41603J | 19 | | | ALL |
| 5109Z | | | GY | | 0-0 | 34-61-21 | D41083J | 10 | | | D41603J | 20 | | | ALL |
| 5110B | 24 | G2 | GZ | | 2-7 | 34-61-21 | D41603J | 23 | | | TB0203Y | C063 | BJ | | ALL |
| 5110R | 24 | G2 | GZ | | 0-0 | 34-61-21 | D41603J | 24 | | | TB0203Y | C064 | BJ | | ALL |
| 5110Z | | | GZ | | 0-0 | 34-61-21 | D41603J | 22 | | | GD01909 | ST.. | 2 | | ALL |
| 5111B | 24 | G2 | HA | | 3-0 | 34-61-21 | D00177A | B13 | | | D41603J | 26 | | | 001-099 |
| 5111B | 24 | G2 | HA | | 3-0 | 34-61-21 | D41603J | 26 | | | D00177A | B13 | | | 115-199 |
| 5111R | 24 | G2 | HA | | 0-0 | 34-61-21 | D00177A | A13 | | | D41603J | 25 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 89

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5111R | 24 | G2 | | HA | 0-0 | 34-61-21 | D41603J | 25 | | | D00177A | A13 | | | 115-199 |
| 5111Z | | | | HA | 0-0 | 34-61-21 | D00177A | DED | | | D41603J | | | AR | 001-099 |
| 5111Z | | | | HA | 0-0 | 34-61-21 | D41603J | | | AR | D00177A | DED | | | 115-199 |
| 5112B | 24 | G2 | | HB | 3-4 | 34-61-23 | D00177A | B01 | | | D41565J | 24 | | | 001-099 |
| 5112B | 24 | G2 | | HB | 3-5 | 34-61-23 | D41565J | 24 | | | D00177A | B01 | | | 115-199 |
| 5112R | 24 | G2 | | HB | 0-0 | 34-61-23 | D00177A | A01 | | | D41565J | 23 | | | 001-099 |
| 5112R | 24 | G2 | | HB | 0-0 | 34-61-23 | D41565J | 23 | | | D00177A | A01 | | | 115-199 |
| 5112Z | | | | HB | 0-0 | 34-61-23 | D00177A | DED | | | D41565J | | | AS | 001-099 |
| 5112Z | | | | HB | 0-0 | 34-61-23 | D41565J | | | AS | D00177A | DED | | | 115-199 |
| 5113B | 24 | G2 | | HC | 3-4 | 34-61-23 | D00177A | E01 | | | D41565J | 13 | | | 001-099 |
| 5113B | 24 | G2 | | HC | 3-5 | 34-61-23 | D41565J | 13 | | | D00177A | E01 | | | 115-199 |
| 5113R | 24 | G2 | | HC | 0-0 | 34-61-23 | D00177A | D01 | | | D41565J | 12 | | | 001-099 |
| 5113R | 24 | G2 | | HC | 0-0 | 34-61-23 | D41565J | 12 | | | D00177A | D01 | | | 115-199 |
| 5113Z | | | | HC | 0-0 | 34-61-23 | D00177A | DED | | | D41565J | | | AT | 001-099 |
| 5113Z | | | | HC | 0-0 | 34-61-23 | D41565J | | | AT | D00177A | DED | | | 115-199 |
| 5114B | 24 | G2 | | HD | 3-4 | 34-61-23 | D00177A | E07 | | | D41565J | 16 | | | 001-099 |
| 5114B | 24 | G2 | | HD | 3-5 | 34-61-23 | D41565J | 16 | | | D00177A | E07 | | | 115-199 |
| 5114R | 24 | G2 | | HD | 0-0 | 34-61-23 | D00177A | D07 | | | D41565J | 15 | | | 001-099 |
| 5114R | 24 | G2 | | HD | 0-0 | 34-61-23 | D41565J | 15 | | | D00177A | D07 | | | 115-199 |
| 5114Z | | | | HD | 0-0 | 34-61-23 | D00177A | DED | | | D41565J | | | AU | 001-099 |
| 5114Z | | | | HD | 0-0 | 34-61-23 | D41565J | | | AU | D00177A | DED | | | 115-199 |
| 5115B | 24 | G2 | | HE | 3-4 | 34-61-23 | D00177A | B03 | | | D41565J | 19 | | | 001-099 |
| 5115B | 24 | G2 | | HE | 3-5 | 34-61-23 | D41565J | 19 | | | D00177A | B03 | | | 115-199 |
| 5115R | 24 | G2 | | HE | 0-0 | 34-61-23 | D00177A | A03 | | | D41565J | 18 | | | 001-099 |
| 5115R | 24 | G2 | | HE | 0-0 | 34-61-23 | D41565J | 18 | | | D00177A | A03 | | | 115-199 |
| 5115Z | | | | HE | 0-0 | 34-61-23 | D00177A | DED | | | D41565J | | | AV | 001-099 |
| 5115Z | | | | HE | 0-0 | 34-61-23 | D41565J | | | AV | D00177A | DED | | | 115-199 |
| 5116B | 24 | G2 | | HH | 4-0 | 31-25-11 | D00177B | E03 | | | D42085J | 39 | | | 001-099 |
| 5116B | 24 | G2 | | HH | 4-0 | 31-25-11 | D42085J | 39 | | | D00177B | E03 | | | 115-199 |
| 5116R | 24 | G2 | | HH | 0-0 | 31-25-11 | D00177B | D03 | | | D42085J | 38 | | | 001-099 |
| 5116R | 24 | G2 | | HH | 0-0 | 31-25-11 | D42085J | 38 | | | D00177B | D03 | | | 115-199 |
| 5116Z | | | | HH | 0-0 | 31-25-11 | D00177B | DED | | | D42085J | | | BD | 001-099 |
| 5116Z | | | | HH | 0-0 | 31-25-11 | D42085J | | | BD | D00177B | DED | | | 115-199 |
| 5117B | 24 | G2 | | HI | 4-4 | 22-41-11 | D00075B | C04 | | | D41345J | 43 | | | 001-099 |
| 5117B | 24 | G2 | | HI | 4-5 | 22-41-11 | D41345J | 43 | | | D00075B | C04 | | | 115-199 |
| 5117R | 24 | G2 | | HI | 0-0 | 22-41-11 | D00075B | C03 | | | D41345J | 42 | | | 001-099 |
| 5117R | 24 | G2 | | HI | 0-0 | 22-41-11 | D41345J | 42 | | | D00075B | C03 | | | 115-199 |
| 5117Z | | | | HI | 0-0 | 22-41-11 | D00075B | DED | | | D41345J | | | AW | 001-099 |
| 5117Z | | | | HI | 0-0 | 22-41-11 | D41345J | | | AW | D00075B | DED | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 90

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | |
| 5118B | 24 | G2 | HJ | | 3-6 | 34-12-62 | D41345J | 28 | | | D42233J | 4 | | | 001-099 |
| 5118B | 24 | G2 | HJ | | 3-7 | 34-12-62 | D41345J | 28 | | | D42233J | 4 | | | 115-199 |
| 5118R | 24 | G2 | HJ | | 0-0 | 34-12-62 | D41345J | 27 | | | D42233J | 5 | | | ALL |
| 5118Z | | | HJ | | 0-0 | 34-12-62 | D41345J | 29 | | | D42233J | | HJ | | ALL |
| 5119B | 24 | G2 | HK | | 4-10 | 34-22-28 | D00083D | B05 | | | D41881J | 14 | | | 001-099 |
| 5119B | 24 | G2 | HK | | 4-6 | 34-22-28 | D41881J | 14 | | | D00083D | B05 | | | 115-199 |
| 5119R | 24 | G2 | HK | | 0-0 | 34-22-28 | D00083D | A05 | | | D41881J | 13 | | | 001-099 |
| 5119R | 24 | G2 | HK | | 0-0 | 34-22-28 | D41881J | 13 | | | D00083D | A05 | | | 115-199 |
| 5119Z | | | HK | | 0-0 | 34-22-28 | D00083D | DED | | | D41881J | | AX | | 001-099 |
| 5119Z | | | HK | | 0-0 | 34-22-28 | D41881J | | AX | | D00083D | DED | | | 115-199 |
| 5120B | 24 | G2 | HW | | 2-5 | 34-51-21 | D43007J | 6 | | | TB0203Y | A073 | BJ | | 001-099 |
| 5120B | 24 | G2 | HW | | 2-10 | 34-51-21 | D41829J | 5 | | | TB0203Y | A073 | BJ | | 115-199 |
| 5120R | 24 | G2 | HW | | 0-0 | 34-51-21 | D43007J | 5 | | | TB0203Y | A074 | BJ | | 001-099 |
| 5120R | 24 | G2 | HW | | 0-0 | 34-51-21 | D41829J | 4 | | | TB0203Y | A074 | BJ | | 115-199 |
| 5120Z | | | HW | | 0-0 | 34-51-21 | D43007J | 7 | | | GD01910 | ST.. | 2 | | 001-099 |
| 5120Z | | | HW | | 0-0 | 34-51-21 | D41829J | 6 | | | GD01910 | ST.. | 2 | | 115-199 |
| 5121B | 24 | G2 | HX | | 4-5 | 34-22-91 | D42085J | 9 | | | TB0203Z | 87 | BJ | | 001-099 |
| 5121B | 24 | G2 | HX | | 4-3 | 34-22-93 | D42087J | 15 | | | TB0203Z | 87 | BJ | | 115-199 |
| 5121R | 24 | G2 | HX | | 0-0 | 34-22-91 | D42085J | 8 | | | TB0203Z | 88 | BJ | | 001-099 |
| 5121R | 24 | G2 | HX | | 0-0 | 34-22-93 | D42087J | 14 | | | TB0203Z | 88 | BJ | | 115-199 |
| 5121Z | | | HX | | 0-0 | 34-22-91 | D42085J | 10 | | | GD01912 | ST.. | 2 | | 001-099 |
| 5121Z | | | HX | | 0-0 | 34-22-93 | D42087J | 16 | | | GD01912 | ST.. | 2 | | 115-199 |
| 5123B | 24 | G2 | IE | | 2-8 | 34-51-21 | D43007J | 3 | | | TB0203Y | A042 | BJ | | 001-099 |
| 5123B | 24 | G2 | IE | | 3-0 | 34-51-21 | D41829J | 2 | | | TB0203Y | A042 | BJ | | 115-199 |
| 5123R | 24 | G2 | IE | | 0-0 | 34-51-21 | D43007J | 2 | | | TB0203Y | A041 | BJ | | 001-099 |
| 5123R | 24 | G2 | IE | | 0-0 | 34-51-21 | D41829J | 1 | | | TB0203Y | A041 | BJ | | 115-199 |
| 5123Z | | | IE | | 0-0 | 34-51-21 | D43007J | 4 | | | GD01906 | ST.. | 2 | | 001-099 |
| 5123Z | | | IE | | 0-0 | 34-51-21 | D41829J | 3 | | | GD01906 | ST.. | 2 | | 115-199 |
| 5124B | 24 | G2 | ID | | 4-10 | 34-25-11 | D41881J | 27 | | | D00083E | B13 | | | 001, 003-009 |
| 5124B | 24 | G2 | ID | | 4-10 | 34-25-11 | TB0203Y | C067 | BJ | | D00083E | B13 | | | 010-099 |
| 5124B | 24 | G2 | IN | | 4-6 | 34-25-11 | D41881J | 27 | | | D00083E | B13 | | | 115-199 |
| 5124R | 24 | G2 | ID | | 0-0 | 34-25-11 | D41881J | 26 | | | D00083E | A13 | | | 001, 003-009 |
| 5124R | 24 | G2 | ID | | 0-0 | 34-25-11 | TB0203Y | C068 | BJ | | D00083E | A13 | | | 010-099 |
| 5124R | 24 | G2 | IN | | 0-0 | 34-25-11 | D41881J | 26 | | | D00083E | A13 | | | 115-199 |
| 5124Z | | | ID | | 0-0 | 34-25-11 | D41881J | | | ID | D00083E | DED | | | 001, 003-009 |
| 5124Z | | | ID | | 0-0 | 34-25-11 | GD01910 | ST.. | 2 | | D00083E | DED | | | 010-099 |
| 5124Z | | | IN | | 0-0 | 34-25-11 | D41881J | | | BE | D00083E | DED | | | 115-199 |
| 5125B | 24 | G2 | IS | | 2-2 | SPARE | D41881J | 34 | | | TB0203Z | 105 | BJ | | 115-199 |
| 5125R | 24 | G2 | IS | | 0-0 | SPARE | D41881J | 33 | | | TB0203Z | 106 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 91

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|-----------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | | |
| 5125Z | | | | IS | 0-0 | SPARE | D41881J | 32 | | | | GD01916 | ST.. | 2 | | 115-199 |
| 5126B | | 24 | G2 | LX | 2-6 | 31-31-43 | D41881J | 33 | | | | TB0203Z | 96 | BJ | | 001-099 |
| 5126B | | 24 | G2 | IH | 2-5 | 31-31-22 | D41881J | 36 | | | | TB0203Z | 79 | BJ | | 115-199 |
| 5126R | | 24 | G2 | LX | 0-0 | 31-31-43 | D41881J | 32 | | | | TB0203Z | 97 | BJ | | 001-099 |
| 5126R | | 24 | G2 | IH | 0-0 | 31-31-22 | D41881J | 35 | | | | TB0203Z | 80 | BJ | | 115-199 |
| 5126Z | | | | LX | 0-0 | 31-31-43 | D41881J | 34 | | | | GD01913 | ST.. | 2 | | 001-099 |
| 5126Z | | | | IH | 0-0 | 31-31-22 | D41881J | 37 | | | | GD01910 | ST.. | 2 | | 115-199 |
| 5127B | | 24 | G2 | LW | 2-7 | 31-31-43 | D41881J | 42 | | | | TB0203Y | C090 | BJ | | 001-099 |
| 5127B | | 24 | G2 | II | 2-2 | 31-31-22 | D41881J | 40 | | | | TB0203Y | C090 | BJ | | 115-199 |
| 5127R | | 24 | G2 | LW | 0-0 | 31-31-43 | D41881J | 41 | | | | TB0203Y | C091 | BJ | | 001-099 |
| 5127R | | 24 | G2 | II | 0-0 | 31-31-22 | D41881J | 39 | | | | TB0203Y | C091 | BJ | | 115-199 |
| 5127Z | | | | LW | 0-0 | 31-31-43 | D41881J | 43 | | | | GD01912 | ST.. | 2 | | 001-099 |
| 5127Z | | | | II | 0-0 | 31-31-22 | D41881J | 38 | | | | GD01911 | ST.. | 2 | | 115-199 |
| 5128B | | 24 | G2 | IJ | 3-2 | 31-31-22 | D41881J | 43 | | | | D00075B | D02 | | | 115-199 |
| 5128R | | 24 | G2 | IJ | 0-0 | 31-31-22 | D41881J | 42 | | | | D00075B | D01 | | | 115-199 |
| 5128Z | | | | IJ | 0-0 | 31-31-22 | D41881J | | | BF | | D00075B | DED | | | 115-199 |
| 5129B | | 24 | G2 | IK | 3-2 | 34-22-81 | D42035J | 30 | | | | D41881J | 28 | | | 001-099 |
| 5129B | | 24 | G2 | IK | 2-10 | 34-22-83 | D42035J | 30 | | | | D41881J | 44 | | | 115-199 |
| 5129R | | 24 | G2 | IK | 0-0 | 34-22-81 | D42035J | 29 | | | | D41881J | 29 | | | 001-099 |
| 5129R | | 24 | G2 | IK | 0-0 | 34-22-83 | D42035J | 29 | | | | D41881J | 45 | | | 115-199 |
| 5129Z | | | | IK | 0-0 | 34-22-81 | D42035J | 31 | | | | D41881J | 30 | | | 001-099 |
| 5129Z | | | | IK | 0-0 | 34-22-83 | D42035J | 31 | | | | D41881J | 46 | | | 115-199 |
| 5130B | | 24 | G2 | IL | 4-5 | 34-55-21 | D42085J | 54 | | | | TB0203Y | C096 | BJ | | 115-199 |
| 5130R | | 24 | G2 | IL | 0-0 | 34-55-21 | D42085J | 53 | | | | TB0203Y | C097 | BJ | | 115-199 |
| 5130Z | | | | IL | 0-0 | 34-55-21 | D42085J | 55 | | | | GD01914 | ST.. | 2 | | 115-199 |
| 5131B | | 24 | G2 | IM | 4-5 | 34-22-91 | D42085J | 54 | | | | TB0203Z | 96 | BJ | | 001-099 |
| 5131R | | 24 | G2 | IM | 0-0 | 34-22-91 | D42085J | 53 | | | | TB0203Z | 97 | BJ | | 001-099 |
| 5131Z | | | | IM | 0-0 | 34-22-91 | D42085J | 55 | | | | GD01914 | ST.. | 2 | | 001-099 |
| 5135B | | 24 | G2 | FE | 2-9 | 22-12-21 | D00075A | B10 | | | | TB0203Z | 119 | BJ | | ALL |
| 5135R | | 24 | G2 | FE | 0-0 | 22-12-21 | D00075A | A10 | | | | TB0203Z | 120 | BJ | | ALL |
| 5135Z | | | | FE | 0-0 | 22-12-21 | D00075A | DED | | | | GD01916 | ST.. | 2 | | ALL |
| 5136B | | 24 | G2 | JC | 3-7 | 34-46-12 | D41431J | 9 | | | | D41063J | 15 | | | 009 |
| 5136B | | 24 | G2 | IR | 3-5 | 34-46-12 | D41431J | 27 | | | | D41063J | 15 | | | 115-199 |
| 5136R | | 24 | G2 | JC | 0-0 | 34-46-12 | D41431J | 8 | | | | D41063J | 14 | | | 009 |
| 5136R | | 24 | G2 | IR | 0-0 | 34-46-12 | D41431J | 26 | | | | D41063J | 14 | | | 115-199 |
| 5136Z | | | | JC | 0-0 | 34-46-12 | D41431J | 10 | | | | D41063J | 16 | | | 009 |
| 5136Z | | | | IR | 0-0 | 34-46-12 | D41431J | 28 | | | | D41063J | 16 | | | 115-199 |
| 5137B | | 24 | G2 | IZ | 2-5 | 31-51-33 | D41907J | 20 | | | | TB0203Z | 105 | BJ | | 001-099 |
| 5137B | | 24 | G2 | IZ | 2-9 | 31-51-33 | D41907J | 20 | | | | TB0203Z | 105 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 92

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | |
| 5137R | 24 | G2 | IZ | | 0-0 | 31-51-33 | D41907J | 19 | | | TB0203Z | 106 | BJ | | ALL |
| 5137Z | | | IZ | | 0-0 | 31-51-33 | D41907J | 21 | | | GD01914 | ST.. | 2 | | 001-099 |
| 5137Z | | | IZ | | 0-0 | 31-51-33 | D41907J | 21 | | | GD01915 | ST.. | 2 | | 115-199 |
| 5138B | 24 | G2 | JA | | 6-0 | 34-12-22 | D00291B | B04 | | | TB0203Z | 109 | BJ | | ALL |
| 5138R | 24 | G2 | JA | | 0-0 | 34-12-22 | D00291B | A04 | | | TB0203Z | 110 | BJ | | ALL |
| 5138Z | | | JA | | 0-0 | 34-12-22 | D00291B | DED | | | GD01915 | ST.. | 2 | | ALL |
| 5139B | 24 | G2 | JB | | 2-9 | 34-21-11 | D41095J | 38 | | | TB0203Z | 105 | BJ | | ALL |
| 5139R | 24 | G2 | JB | | 0-0 | 34-21-11 | D41095J | 37 | | | TB0203Z | 106 | BJ | | ALL |
| 5139Z | | | JB | | 0-0 | 34-21-11 | D41095J | 39 | | | GD01914 | ST.. | 2 | | 001-099 |
| 5139Z | | | JB | | 0-0 | 34-21-11 | D41095J | 39 | | | GD01916 | ST.. | 2 | | 115-199 |
| 5140B | 24 | G2 | AA | | 2-6 | 22-24-11 | D41907J | 24 | | | TB0203Z | 109 | BJ | | 001-099 |
| 5140B | 24 | G2 | AA | | 2-10 | 22-24-11 | D41907J | 24 | | | TB0203Z | 109 | BJ | | 115-199 |
| 5140R | 24 | G2 | AA | | 0-0 | 22-24-11 | D41907J | 23 | | | TB0203Z | 110 | BJ | | ALL |
| 5140Z | | | AA | | 0-0 | 22-24-11 | D41907J | 25 | | | GD01914 | ST.. | 2 | | ALL |
| 5141B | 24 | G2 | JG | | 4-0 | 22-33-11 | D41907J | 31 | | | TB0203Y | C030 | BJ | | 001-099 |
| 5141B | 24 | G2 | JG | | 4-4 | 22-33-11 | D41907J | 31 | | | TB0203Y | C030 | BJ | | 115-199 |
| 5141R | 24 | G2 | JG | | 0-0 | 22-33-11 | D41907J | 30 | | | TB0203Y | A030 | BJ | | ALL |
| 5141Z | | | JG | | 0-0 | 22-33-11 | D41907J | 32 | | | GD01904 | ST.. | 2 | | ALL |
| 5142B | 24 | G2 | JH | | 3-4 | 34-61-24 | D00177A | H03 | | | TB0203Y | C030 | BJ | | ALL |
| 5142R | 24 | G2 | JH | | 0-0 | 34-61-24 | D00177A | G03 | | | TB0203Y | A030 | BJ | | ALL |
| 5142Z | | | JH | | 0-0 | 34-61-24 | D00177A | DED | | | GD01904 | ST.. | 2 | | ALL |
| 5143B | 24 | G2 | KD | | 3-1 | 34-61-15 | D41095J | 18 | | | TB0203Z | 82 | BJ | | ALL |
| 5143R | 24 | G2 | KD | | 0-0 | 34-61-15 | D41095J | 17 | | | TB0203Z | 83 | BJ | | ALL |
| 5143Z | | | KD | | 0-0 | 34-61-15 | D41095J | 19 | | | GD01910 | ST.. | 2 | | ALL |
| 5144B | 24 | G2 | KE | | 3-6 | 34-61-25 | D41907J | 35 | | | TB0203Y | A042 | BJ | | 001-099 |
| 5144B | 24 | G2 | KE | | 3-9 | 34-61-25 | D41907J | 35 | | | TB0203Y | A042 | BJ | | 115-199 |
| 5144R | 24 | G2 | KE | | 0-0 | 34-61-25 | D41907J | 34 | | | TB0203Y | A041 | BJ | | ALL |
| 5144Z | | | KE | | 0-0 | 34-61-25 | D41907J | 33 | | | GD01906 | ST.. | 2 | | ALL |
| 5145B | 24 | G2 | KF | | 2-8 | 34-61-25 | D41907J | 36 | | | TB0203Z | 79 | BJ | | 001-099 |
| 5145B | 24 | G2 | KF | | 3-0 | 34-61-25 | D41907J | 36 | | | TB0203Z | 79 | BJ | | 115-199 |
| 5145R | 24 | G2 | KF | | 0-0 | 34-61-25 | D41907J | 37 | | | TB0203Z | 80 | BJ | | ALL |
| 5145Z | | | KF | | 0-0 | 34-61-25 | D41907J | 38 | | | GD01911 | ST.. | 2 | | ALL |
| 5151B | 24 | G2 | LA | | 3-9 | 34-22-19 | D41603J | 36 | | | TB0203Z | 113 | BJ | | ALL |
| 5151R | 24 | G2 | LA | | 0-0 | 34-22-19 | D41603J | 35 | | | TB0203Z | 114 | BJ | | ALL |
| 5151Z | | | LA | | 0-0 | 34-22-19 | D41603J | 37 | | | GD01916 | ST.. | 2 | | ALL |
| 5152B | 24 | G2 | LB | | 4-10 | 34-22-29 | D00083D | K01 | | | TB0203Z | 109 | BJ | | ALL |
| 5152R | 24 | G2 | LB | | 0-0 | 34-22-29 | D00083D | J01 | | | TB0203Z | 110 | BJ | | ALL |
| 5152Z | | | LB | | 0-0 | 34-22-29 | D00083D | DED | | | GD01915 | ST.. | 2 | | ALL |
| 5153B | 24 | G2 | LC | | 5-1 | 34-22-29 | D00083A | K01 | | | D41095J | 25 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 93

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5153B | 24 | G2 | LC | | 5-1 | 34-22-29 | D00083A | K01 | | | D41095J | 54 | | | 115-199 |
| 5153R | 24 | G2 | LC | | 0-0 | 34-22-29 | D00083A | J01 | | | D41095J | 24 | | | 001-099 |
| 5153R | 24 | G2 | LC | | 0-0 | 34-22-29 | D00083A | J01 | | | D41095J | 53 | | | 115-199 |
| 5153Z | | | LC | | 0-0 | 34-22-29 | D00083A | DED | | | D41095J | | LC | | ALL |
| 5154B | 24 | G2 | LD | | 5-1 | 34-22-29 | D00083D | B07 | | | D41095J | 23 | | | 001-099 |
| 5154B | 24 | G2 | LD | | 5-1 | 34-22-29 | D00083D | B07 | | | D41095J | 42 | | | 115-199 |
| 5154R | 24 | G2 | LD | | 0-0 | 34-22-29 | D00083D | A07 | | | D41095J | 41 | | | ALL |
| 5154Z | | | LD | | 0-0 | 34-22-29 | D00083D | DED | | | D41095J | | LD | | ALL |
| 5158B | 24 | G2 | LT | | 2-8 | 27-32-21 | D41345J | 54 | | | TB0203Z | 82 | BJ | | 001-099 |
| 5158R | 24 | G2 | LT | | 0-0 | 27-32-21 | D41345J | 53 | | | TB0203Z | 83 | BJ | | 001-099 |
| 5158Z | | | LT | | 0-0 | 27-32-21 | D41345J | 55 | | | GD01910 | ST.. | 2 | | 001-099 |
| 5162B | 24 | G2 | LE | | 3-2 | 34-45-01 | D41347J | 47 | | | D00083D | K09 | | | 001-099 |
| 5162B | 24 | G2 | LL | | 3-1 | 34-45-01 | D41347J | 47 | | | D00083A | REF | VM | | 115-199 |
| 5162R | 24 | G2 | LE | | 0-0 | 34-45-01 | D41347J | 46 | | | D00083D | J09 | | | 001-099 |
| 5162R | 24 | G2 | LL | | 0-0 | 34-45-01 | D41347J | 46 | | | D00083A | REF | VM | | 115-199 |
| 5162Z | | | LE | | 0-0 | 34-45-01 | D41347J | | | LE | D00083D | DED | | | 001-099 |
| 5162Z | | | LL | | 0-0 | 34-45-01 | D41347J | | | LL | D00083A | DED | | | 115-199 |
| 5173B | 22 | GU | MB | | 5-0 | 34-25-12 | D00083A | D02 | | | D41200J | 5 | | | 002 |
| 5173R | 22 | GU | MB | | 0-0 | 34-25-12 | D00083A | C02 | | | D41200J | 4 | | | 002 |
| 5173Z | | | MB | | 0-0 | 34-25-12 | D00083A | DED | | | D41200J | | MB | | 002 |
| 5174B | 22 | GU | MC | | 5-0 | 34-25-12 | D00083D | D02 | | | D41200J | 8 | | | 002 |
| 5174R | 22 | GU | MC | | 0-0 | 34-25-12 | D00083D | C02 | | | D41200J | 7 | | | 002 |
| 5174Z | | | MC | | 0-0 | 34-25-12 | D00083D | DED | | | D41200J | | MC | | 002 |
| 5175B | 22 | GU | MD | | 5-0 | 34-25-12 | D41200J | 10 | | | TB0203Y | C067 | BJ | | 002 |
| 5175R | 22 | GU | MD | | 0-0 | 34-25-12 | D41200J | 11 | | | TB0203Y | C068 | BJ | | 002 |
| 5175Z | | | MD | | 0-0 | 34-25-12 | D41200J | 12 | | | TB0203Y | A068 | BJ | | 002 |
| 5177B | 22 | GU | MH | | 5-0 | 34-25-12 | D41200J | 2 | | | TB0203Y | C067 | BJ | | 002 |
| 5177R | 22 | GU | MH | | 0-0 | 34-25-12 | D41200J | 1 | | | TB0203Y | C068 | BJ | | 002 |
| 5177Z | | | MH | | 0-0 | 34-25-12 | D41200J | 3 | | | TB0203Y | A068 | BJ | | 002 |
| 5181B | 24 | G2 | LE | | 4-0 | 34-22-28 | D00083A | H06 | | | D41565J | 54 | | | 115-199 |
| 5181R | 24 | G2 | LE | | 0-0 | 34-22-28 | D00083A | G06 | | | D41565J | 53 | | | 115-199 |
| 5181Z | | | LE | | 0-0 | 34-22-28 | D00083A | DED | | | D41565J | | LE | | 115-199 |
| 5182B | 24 | G2 | LF | | 2-10 | 34-22-28 | D41829J | 9 | | | TB0203Y | C075 | BJ | | 115-199 |
| 5182R | 24 | G2 | LF | | 0-0 | 34-22-28 | D41829J | 8 | | | TB0203Y | A075 | BJ | | 115-199 |
| 5182Z | | | LF | | 0-0 | 34-22-28 | D41829J | 10 | | | GD01910 | ST.. | 2 | | 115-199 |
| 5183B | 24 | G2 | LG | | 3-11 | 34-22-28 | D00083D | H06 | | | TB0203Y | C075 | BJ | | 115-199 |
| 5183R | 24 | G2 | LG | | 0-0 | 34-22-28 | D00083D | G06 | | | TB0203Y | A075 | BJ | | 115-199 |
| 5183Z | | | LG | | 0-0 | 34-22-28 | D00083D | DED | | | GD01910 | ST.. | 2 | | 115-199 |
| 5184B | 24 | G2 | LH | | 2-9 | 34-22-38 | D41679J | 26 | | | TB0203Y | C075 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 94

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5184R | 24 | G2 | LH | | 0-0 | 34-22-38 | D41679J | 25 | | | TB0203Y | A075 | BJ | | 115-199 |
| 5184Z | | | LH | | 0-0 | 34-22-38 | D41679J | 27 | | | GD01912 | ST.. | 2 | | 115-199 |
| 5186B | 24 | G2 | LK | | 2-9 | 34-22-18 | D41603J | 54 | | | D42085J | 51 | | | 115-199 |
| 5186R | 24 | G2 | LK | | 0-0 | 34-22-18 | D41603J | 52 | | | D42085J | 50 | | | 115-199 |
| 5186Z | | | LK | | 0-0 | 34-22-18 | D41603J | 55 | | | D42085J | | | LK | 115-199 |
| 5193B | 22 | GU | KZ | | 5-0 | 34-58-11 | D00177B | B07 | | | D41907J | 7 | | | 115-199 |
| 5193R | 22 | GU | KZ | | 0-0 | 34-58-11 | D00177B | A07 | | | D41907J | 6 | | | 115-199 |
| 5193Z | | | KZ | | 0-0 | 34-58-11 | D00177B | DED | | | D41907J | 8 | | | 115-199 |
| 5194B | 22 | GU | KY | | 5-0 | 34-58-21 | D00177A | B15 | | | D02941B | D02 | | | 115-199 |
| 5194R | 22 | GU | KY | | 0-0 | 34-58-21 | D00177A | A15 | | | D02941B | C02 | | | 115-199 |
| 5194Z | | | KY | | 0-0 | 34-58-21 | D00177A | DED | | | D02941B | DED | | | 115-199 |
| 5195B | 22 | GU | JI | | 5-0 | 34-58-21 | D02941B | K02 | | | D41565J | 50 | | | 115-199 |
| 5195R | 22 | GU | JI | | 0-0 | 34-58-21 | D02941B | J02 | | | D41565J | 49 | | | 115-199 |
| 5195Z | | | JI | | 0-0 | 34-58-21 | D02941B | DED | | | D41565J | | | BL | 115-199 |
| 5196B | 22 | GU | KW | | 5-0 | 34-58-21 | D02941B | B08 | | | D41881J | 51 | | | 115-199 |
| 5196R | 22 | GU | KW | | 0-0 | 34-58-21 | D02941B | A08 | | | D41881J | 50 | | | 115-199 |
| 5196Z | | | KW | | 0-0 | 34-58-21 | D02941B | DED | | | D41881J | | | BN | 115-199 |
| 5197B | 22 | GU | KV | | 5-0 | 34-58-21 | D02941B | H08 | | | D41393J | 38 | | | 115-199 |
| 5197R | 22 | GU | KV | | 0-0 | 34-58-21 | D02941B | G08 | | | D41393J | 39 | | | 115-199 |
| 5197Z | | | KV | | 0-0 | 34-58-21 | D02941B | DED | | | D41393J | | | BM | 115-199 |
| 5207B | 24 | G2 | MA | | 2-4 | 34-61-21 | D41083J | 20 | | | TB0203Z | 58 | BJ | | 001-099 |
| 5207R | 24 | G2 | MA | | 0-0 | 34-61-21 | D41083J | 19 | | | TB0203Z | 59 | BJ | | 001-099 |
| 5207Z | | | MA | | 0-0 | 34-61-21 | D41083J | 21 | | | GD01908 | ST.. | 2 | | 001-099 |
| 5208B | 24 | G2 | LL | | 3-3 | 34-61-14 | D41743J | 30 | | | TB0203Z | 58 | BJ | | 001-099 |
| 5208R | 24 | G2 | LL | | 0-0 | 34-61-14 | D41743J | 29 | | | TB0203Z | 59 | BJ | | 001-099 |
| 5208Z | | | LL | | 0-0 | 34-61-14 | D41743J | 31 | | | GD01908 | ST.. | 2 | | 001-099 |
| 5212B | 24 | G2 | LM | | 3-11 | 34-61-24 | D41679J | 54 | | | D00177B | E09 | | | 001-099 |
| 5212R | 24 | G2 | LM | | 0-0 | 34-61-24 | D41679J | 53 | | | D00177B | D09 | | | 001-099 |
| 5212Z | | | LM | | 0-0 | 34-61-24 | D41679J | | | LM | D00177B | DED | | | 001-099 |
| 5221B | 22 | GU | JL | | 4-0 | 34-43-14 | D41063J | 23 | | | TB0203Z | 113 | BJ | | 002 |
| 5221R | 22 | GU | JL | | 0-0 | 34-43-14 | D41063J | 22 | | | TB0203Z | 114 | BJ | | 002 |
| 5221Z | | | JL | | 0-0 | 34-43-14 | D41063J | 24 | | | GD01916 | ST.. | 2 | | 002 |
| 5239B | 22 | GU | NX | | 6-0 | 34-22-28 | D00083E | B14 | | | D22001J | 23 | | | 002 |
| 5239R | 22 | GU | NX | | 0-0 | 34-22-28 | D00083E | A14 | | | D22001J | 22 | | | 002 |
| 5239Z | | | NX | | 0-0 | 34-22-28 | D00083E | DED | | | D22001J | | | BG | 002 |
| 5241B | 22 | GU | OB | | 5-0 | 34-46-12 | D00083D | D08 | | | D41431J | 9 | | | 002 |
| 5241R | 22 | GU | OB | | 0-0 | 34-46-12 | D00083D | C08 | | | D41431J | 8 | | | 002 |
| 5241Z | | | OB | | 0-0 | 34-46-12 | D00083D | DED | | | D41431J | | | ED | 002 |
| 5242B | 22 | GU | OC | | 4-0 | 34-46-12 | TB0203Z | 113 | BJ | | D41881J | 49 | | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 95

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5242R | 22 | GU | OC | | 0-0 | 34-46-12 | TB0203Z | 114 | BJ | | D41881J | 48 | | | 002 |
| 5242Z | | | OC | | 0-0 | 34-46-12 | GD01916 | ST.. | 2 | | D41881J | 47 | | | 002 |
| 5249B | 22 | GU | PB | | 5-0 | 34-58-21 | D00205B | REF | VP | | D41393J | 18 | | | 002 |
| 5249R | 22 | GU | PB | | 0-0 | 34-58-21 | D00205B | REF | VP | | D41393J | 10 | | | 002 |
| 5249Z | | | PB | | 0-0 | 34-58-21 | D00205B | DED | | | D41393J | | | PB | 002 |
| 5285B | 24 | 7K | AH | | 5-0 | 34-43-15 | D41063J | 2 | | | D22001J | 5 | | | 002 |
| 5285W | 24 | 7K | AH | | 0-0 | 34-43-15 | D41063J | 1 | | | D22001J | 4 | | | 002 |
| 5285Z | | | AH | | 0-0 | 34-43-15 | D41063J | 3 | | | D22001J | 6 | | | 002 |
| 5294B | 22 | GU | OD | | 5-0 | 34-46-12 | TB0203Z | 85 | BJ | | D41881J | 52 | | | 002 |
| 5294R | 22 | GU | OD | | 0-0 | 34-46-12 | TB0203Z | 86 | BJ | | D41881J | 51 | | | 002 |
| 5294Z | | | OD | | 0-0 | 34-46-12 | GD01912 | ST.. | 2 | | D41881J | 50 | | | 002 |
| 5297B | 22 | GU | OE | | 5-0 | 34-43-11 | D22001J | 14 | | | D41063J | 12 | | | 002 |
| 5297R | 22 | GU | OE | | 0-0 | 34-43-11 | D22001J | 13 | | | D41063J | 11 | | | 002 |
| 5297Z | | | OE | | 0-0 | 34-43-11 | D22001J | 15 | | | D41063J | 13 | | | 002 |
| 5310B | 24 | 7K | KO | | 5-0 | 34-43-15 | D00083A | F03 | | | D22001J | 2 | | | 002 |
| 5310W | 24 | 7K | KO | | 0-0 | 34-43-15 | D00083A | E03 | | | D22001J | 1 | | | 002 |
| 5310Z | | | KO | | 0-0 | 34-43-15 | D00083A | DED | | | D22001J | 3 | | | 002 |
| 5311B | 24 | G2 | LU | | 3-2 | 31-31-42 | D41345J | 36 | | | TB0203Z | 85 | BJ | | 001-099 |
| 5311R | 24 | G2 | LU | | 0-0 | 31-31-42 | D41345J | 35 | | | TB0203Z | 86 | BJ | | 001-099 |
| 5311Z | | | LU | | 0-0 | 31-31-42 | D41345J | 37 | | | GD01912 | ST.. | 2 | *1 | 001-099 |
| 5312B | 24 | G2 | LV | | 4-4 | 31-31-42 | D41345J | 50 | | | D00075B | D02 | | | 001-099 |
| 5312R | 24 | G2 | LV | | 0-0 | 31-31-42 | D41345J | 49 | | | D00075B | D01 | | | 001-099 |
| 5312Z | | | LV | | 0-0 | 31-31-42 | D41345J | | LV | | D00075B | DED | | | 001-099 |
| 5313B | 24 | G2 | LY | | 2-7 | 31-31-43 | D41881J | 36 | | | TB0203Z | 87 | BJ | | 001-099 |
| 5313R | 24 | G2 | LY | | 0-0 | 31-31-43 | D41881J | 35 | | | TB0203Z | 88 | BJ | | 001-099 |
| 5313Z | | | LY | | 0-0 | 31-31-43 | D41881J | 37 | | | GD01912 | ST.. | 2 | *1 | 001-099 |
| 5316B | 22 | GU | MG | | 4-0 | 34-25-12 | D00083E | B13 | | | TB0203Y | C067 | BJ | | 002 |
| 5316R | 22 | GU | MG | | 0-0 | 34-25-12 | D00083E | A13 | | | TB0203Y | C068 | BJ | | 002 |
| 5316Z | | | MG | | 0-0 | 34-25-12 | D00083E | DED | | | TB0203Y | | | MG | 002 |
| 5324B | 24 | G2 | LZ | | 2-4 | 31-31-43 | D43007J | 20 | | | TB0203Z | 58 | BJ | | 001-009 |
| 5324R | 24 | G2 | LZ | | 0-0 | 31-31-43 | D43007J | 19 | | | TB0203Z | 59 | BJ | | 001-009 |
| 5324Z | | | LZ | | 0-0 | 31-31-43 | D43007J | 21 | | | GD01908 | ST.. | 2 | | 001-009 |
| 5326B | 22 | GU | RG | | 2-5 | 31-31-41 | D43021J | 21 | | | TB0203Y | C067 | BJ | | 010-099 |
| 5326R | 22 | GU | RG | | 0-0 | 31-31-41 | D43021J | 20 | | | TB0203Y | C068 | BJ | | 010-099 |
| 5326Z | | | RG | | 0-0 | 31-31-41 | D43021J | 22 | | | GD01910 | ST.. | 2 | *1 | 010-099 |
| 5333B | 24 | G2 | SC | | 4-0 | 34-12-61 | D42221J | 3 | | | TB0203Z | 109 | BJ | | ALL |
| 5333R | 24 | G2 | SC | | 0-0 | 34-12-61 | D42221J | 2 | | | TB0203Z | 110 | BJ | | ALL |
| 5333Z | | | SC | | 0-0 | 34-12-61 | D42221J | 4 | | | GD01919 | ST.. | 2 | | ALL |
| 5335B | 24 | G2 | SA | | 4-0 | 34-12-62 | D42233J | 8 | | | TB0203Z | 119 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 96

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| 5335R | 24 | G2 | SA | | 0-0 | 34-12-62 | D42233J | 7 | | | TB0203Z | 120 | BJ | | ALL |
| 5335Z | | | SA | | 0-0 | 34-12-62 | D42233J | 9 | | | GD01919 | ST.. | 2 | | ALL |
| 5336B | 24 | G2 | SB | | 4-0 | 34-12-62 | D42233J | 11 | | | D41095J | 29 | | | 001-099 |
| 5336B | 24 | G2 | SB | | 4-0 | 34-12-62 | D42233J | 11 | | | D41095J | 26 | | | 115-199 |
| 5336R | 24 | G2 | SB | | 0-0 | 34-12-62 | D42233J | 10 | | | D41095J | 27 | | | ALL |
| 5336Z | | | SB | | 0-0 | 34-12-62 | D42233J | | | SB | D41095J | 28 | | | ALL |
| 5337B | 22 | GU | MG | | 3-3 | 34-25-11 | D41881J | 27 | | | TB0203Y | C067 | BJ | | 010-099 |
| 5337R | 22 | GU | MG | | 0-0 | 34-25-11 | D41881J | 26 | | | TB0203Y | C068 | BJ | | 010-099 |
| 5337Z | | | MG | | 0-0 | 34-25-11 | D41881J | 25 | | | GD01910 | ST.. | 2 | *1 | 010-099 |
| 8011 | 22 | GA | | | 3-3 | 31-31-61 | D41881J | 24 | | | TB0203Y | A040 | BJ | | 010-099 |
| 8012 | 22 | GA | | | 2-8 | 34-22-27 | D42085J | 45 | | | TB0203Y | A040 | BJ | | 010-099 |
| 8014 | 22 | GA | | | 3-0 | 34-22-26 | D00083B | D02 | | | GD01905 | ST.. | 2 | | 002 |
| 8022 | 22 | GA | | | 5-0 | 34-22-26 | GD01906 | ST.. | 2 | | D00083B | G06 | | | 002 |
| 8022 | 22 | GA | | | 5-0 | 34-22-26 | GD01902 | ST.. | 2 | | D00083B | G06 | | | 115-199 |
| 8026 | 22 | GA | | | 5-0 | 34-22-26 | GD01906 | ST.. | 2 | | D00083B | E06 | | | 002 |
| 8026 | 22 | GA | | | 4-0 | 34-22-26 | GD01902 | ST.. | 2 | | D00083B | E06 | | | 115-199 |
| 8027 | 22 | GA | | | 5-0 | 34-22-26 | GD01903 | ST.. | 2 | | D00083B | K05 | | | 002 |
| 8041 | 22 | GA | | | 3-0 | 34-22-26 | GD01905 | ST.. | 2 | | D00083A | A14 | | | 002 |
| 8046 | 22 | GA | | | 4-0 | 34-22-26 | GD01905 | ST.. | 2 | | D00083B | J02 | | | 002 |
| A-BL | | | | | 0-0 | 73-21-12 | TB0203A | 17 | | | TB0203Y | A029 | BJ | | ALL |
| A-GR | | | | | 0-0 | 73-21-12 | TB0203A | 17 | | | TB0203Y | A108 | BJ | | ALL |
| A-RD | | | | | 0-0 | 73-21-12 | TB0203A | 17 | | | TB0203Y | A028 | BJ | | ALL |
| A-YL | | | | | 0-0 | 73-21-12 | TB0203A | 17 | | | GD01903 | ST.. | 2 | | ALL |
| B-BL | | | | | 0-0 | 73-21-12 | TB0203A | 19 | | | TB0203Y | A107 | BJ | | ALL |
| B-GR | | | | | 0-0 | 73-21-12 | TB0203A | 19 | | | TB0203Y | C029 | BJ | | ALL |
| B-RD | | | | | 0-0 | 73-21-12 | TB0203A | 19 | | | TB0203Y | C028 | BJ | | ALL |
| B-YL | | | | | 0-0 | 73-21-12 | TB0203A | 19 | | | GD01903 | ST.. | 2 | | ALL |
| FRAA | | | | | 0-0 | 34-22-28 | D41565J | 37 | | | D41565J | | | AA | 001-099 |
| FRAA | | | | | 0-0 | 34-22-28 | D41565J | | | AA | D41565J | 37 | | | 115-199 |
| FRAB | | | | | 0-0 | 34-22-29 | D41345J | 47 | | | D41345J | | | AB | 001-099 |
| FRAB | | | | | 0-0 | 34-22-29 | D41345J | | | AB | D41345J | 47 | | | 115-199 |
| FRAC | | | | | 0-0 | 34-61-11 | D41565J | 1 | | | D41565J | | | AC | 001-099 |
| FRAC | | | | | 0-0 | 34-61-11 | D41565J | | | AC | D41565J | 1 | | | 115-199 |
| FRAD | | | | | 0-0 | 34-61-11 | D41565J | 4 | | | D41565J | | | AD | 001-099 |
| FRAD | | | | | 0-0 | 34-61-11 | D41565J | | | AD | D41565J | 4 | | | 115-199 |
| FRAE | | | | | 0-0 | 34-61-11 | D41565J | 8 | | | D41565J | | | AE | 001-099 |
| FRAE | | | | | 0-0 | 34-61-11 | D41565J | | | AE | D41565J | 8 | | | 115-199 |
| FRAF | | | | | 0-0 | 34-61-22 | D41603J | 30 | | | D41603J | | | AF | 001-099 |
| FRAF | | | | | 0-0 | 34-61-22 | D41603J | | | AF | D41603J | 30 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 97

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| FRAH | | | | | 0-0 | 34-61-24 | D41345J | 13 | | | D41345J | | | AH | 001-099 |
| FRAH | | | | | 0-0 | 34-61-24 | D41345J | | | AH | D41345J | 13 | | | 115-199 |
| FRAO | | | | | 0-0 | 22-12-21 | D41347J | 7 | | | D41347J | | | AO | 001-099 |
| FRAO | | | | | 0-0 | 22-12-21 | D41347J | | | AO | D41347J | 7 | | | 115-199 |
| FRAP | | | | | 0-0 | 22-41-12 | D41095J | 4 | | | D41095J | | | AP | 001-099 |
| FRAP | | | | | 0-0 | 22-41-12 | D41095J | | | AP | D41095J | 4 | | | 115-199 |
| FRAQ | | | | | 0-0 | 34-61-21 | D41083J | 4 | | | D41083J | | | AQ | 001-099 |
| FRAQ | | | | | 0-0 | 34-61-21 | D41083J | | | AQ | D41083J | 4 | | | 115-199 |
| FRAR | | | | | 0-0 | 34-61-21 | D41603J | 27 | | | D41603J | | | AR | 001-099 |
| FRAR | | | | | 0-0 | 34-61-21 | D41603J | | | AR | D41603J | 27 | | | 115-199 |
| FRAS | | | | | 0-0 | 34-61-23 | D41565J | 25 | | | D41565J | | | AS | 001-099 |
| FRAS | | | | | 0-0 | 34-61-23 | D41565J | | | AS | D41565J | 25 | | | 115-199 |
| FRAT | | | | | 0-0 | 34-61-23 | D41565J | 14 | | | D41565J | | | AT | 001-099 |
| FRAT | | | | | 0-0 | 34-61-23 | D41565J | | | AT | D41565J | 14 | | | 115-199 |
| FRAU | | | | | 0-0 | 34-61-23 | D41565J | 17 | | | D41565J | | | AU | 001-099 |
| FRAU | | | | | 0-0 | 34-61-23 | D41565J | | | AU | D41565J | 17 | | | 115-199 |
| FRAV | | | | | 0-0 | 34-61-23 | D41565J | 20 | | | D41565J | | | AV | 001-099 |
| FRAV | | | | | 0-0 | 34-61-23 | D41565J | | | AV | D41565J | 20 | | | 115-199 |
| FRAW | | | | | 0-0 | 22-41-11 | D41345J | 45 | | | D41345J | | | AW | 001-099 |
| FRAW | | | | | 0-0 | 22-41-11 | D41345J | | | AW | D41345J | 45 | | | 115-199 |
| FRAX | | | | | 0-0 | 34-22-28 | D41881J | 15 | | | D41881J | | | AX | 001-099 |
| FRAX | | | | | 0-0 | 34-22-28 | D41881J | | | AX | D41881J | 15 | | | 115-199 |
| FRAY | | | | | 0-0 | 22-13-21 | D41881J | 9 | | | D41881J | | | AY | 001-099 |
| FRAY | | | | | 0-0 | 22-13-21 | D41881J | | | AY | D41881J | 9 | | | 115-199 |
| FRAZ | | | | | 0-0 | 22-15-11 | D41393J | 21 | | | D41393J | | | AZ | 001-099 |
| FRAZ | | | | | 0-0 | 22-15-11 | D41393J | | | AZ | D41393J | 21 | | | 115-199 |
| FRBA | | | | | 0-0 | 22-15-11 | D41347J | 25 | | | D41347J | | | BA | 001-099 |
| FRBA | | | | | 0-0 | 22-15-11 | D41347J | | | BA | D41347J | 25 | | | 115-199 |
| FRBB | | | | | 0-0 | 22-15-11 | D41679J | 41 | | | D41679J | | | BB | 001-099 |
| FRBB | | | | | 0-0 | 22-15-11 | D41679J | | | BB | D41679J | 41 | | | 115-199 |
| FRBC | | | | | 0-0 | 22-15-11 | D41743J | 3 | | | D41743J | | | BC | 001-099 |
| FRBC | | | | | 0-0 | 22-15-11 | D41743J | | | BC | D41743J | 3 | | | 115-199 |
| FRBD | | | | | 0-0 | 31-25-11 | D42085J | 40 | | | D42085J | | | BD | 001-099 |
| FRBD | | | | | 0-0 | 31-25-11 | D42085J | | | BD | D42085J | 40 | | | 115-199 |
| FRBE | | | | | 0-0 | 34-25-11 | D41881J | | | BE | D41881J | 25 | | | 115-199 |
| FRBF | | | | | 0-0 | 31-31-22 | D41881J | | | BF | D41881J | 41 | | | 115-199 |
| FRBG | | | | | 0-0 | 34-22-28 | D22001J | | | BG | D22001J | 24 | | | 002 |
| FRBL | | | | | 0-0 | 34-58-21 | D41565J | | | BL | D41565J | 51 | | | 115-199 |
| FRBM | | | | | 0-0 | 34-58-21 | D41393J | | | BM | D41393J | 18 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 98

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | Description | | From | | To | | | Effectivity | | | | |
|------------|-------------|-------|-----------------------------|-------|----------|---------|------|------|--------|-------------|------|------|--------|--------------|
| Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1173 | 286N1173 | | E2-2 SHELF - R2 (continued) | | | | | | | | | | | |
| FRBN | | | | 0-0 | 34-58-21 | D41881J | | | BN | D41881J | 55 | | | 115-199 |
| FRED | | | | 0-0 | 34-46-12 | D41431J | | | ED | D41431J | 10 | | | 002 |
| FRHJ | | | | 0-0 | 34-12-62 | D42233J | | 6 | | D42233J | | | HJ | ALL |
| FRID | | | | 0-0 | 34-25-11 | D41881J | | | ID | D41881J | 25 | | | 001, 003-009 |
| FRLC | | | | 0-0 | 34-22-29 | D41095J | | 26 | | D41095J | | | LC | 001-099 |
| FRLC | | | | 0-0 | 34-22-29 | D41095J | | 55 | | D41095J | | | LC | 115-199 |
| FRLD | | | | 0-0 | 34-22-29 | D41095J | | 40 | | D41095J | | | LD | ALL |
| FRLE | | | | 0-0 | 34-45-01 | D41347J | | | LE | D41347J | 49 | | | 001-099 |
| FRLE | | | | 0-0 | 34-22-28 | D41565J | | 55 | | D41565J | | | LE | 115-199 |
| FRLK | | | | 0-0 | 34-22-18 | D42085J | | | LK | D42085J | 52 | | | 115-199 |
| FRLI | | | | 0-0 | 34-45-01 | D41347J | | | LL | D41347J | 49 | | | 115-199 |
| FRLM | | | | 0-0 | 34-61-24 | D41679J | | | LM | D41679J | 55 | | | 001-099 |
| FRLV | | | | 0-0 | 31-31-42 | D41345J | | | LV | D41345J | 38 | | | 001-099 |
| FRMB | | | | 0-0 | 34-25-12 | D41200J | | | MB | D41200J | 6 | | | 002 |
| FRMC | | | | 0-0 | 34-25-12 | D41200J | | | MC | D41200J | 9 | | | 002 |
| FRMG | | | | 0-0 | 34-25-12 | GD01909 | ST.. | 2 | | TB0203Y | | | MG | 002 |
| FRMH | | | | 0-0 | 34-25-12 | TB0203Y | A068 | BJ | | TB0203Y | | | MG | 002 |
| FRPB | | | | 0-0 | 34-58-21 | D41393J | | | PB | D41393J | 28 | | | 002 |
| FRSB | | | | 0-0 | 34-12-62 | D42233J | | | SB | D42233J | 12 | | | ALL |
| W1175 | 286N1175 | | E2-3 INTEGRATION BUNDLE | | | | | | | | | | | |
| 0001 | 24 | GK | | 3-9 | 34-22-34 | D00085D | A09 | | | D41605J | 1 | | | 001-099 |
| 0001 | 24 | GK | | 3-0 | 34-22-34 | D41605J | 1 | | | D00085D | A09 | | | 115-199 |
| 0002 | 24 | GK | | 3-9 | 34-22-34 | D00085D | B09 | | | D41605J | 2 | | | 001-099 |
| 0002 | 24 | GK | | 3-0 | 34-22-34 | D41605J | 2 | | | D00085D | B09 | | | 115-199 |
| 0003 | 24 | GK | | 3-9 | 34-22-34 | D00085D | C09 | | | D41605J | 3 | | | 001-099 |
| 0003 | 24 | GK | | 3-0 | 34-22-34 | D41605J | 3 | | | D00085D | C09 | | | 115-199 |
| 0004 | 24 | GK | | 3-9 | 34-22-34 | D00085D | F09 | | | D41605J | 4 | | | 001-099 |
| 0004 | 24 | GK | | 3-0 | 34-22-34 | D41605J | 4 | | | D00085D | F09 | | | 115-199 |
| 0005 | 24 | GK | | 3-9 | 34-22-34 | D00085D | G09 | | | D41605J | 5 | | | 001-099 |
| 0005 | 24 | GK | | 3-0 | 34-22-34 | D41605J | 5 | | | D00085D | G09 | | | 115-199 |
| 0006 | 24 | GK | | 3-9 | 34-22-34 | D00085D | H09 | | | D41605J | 6 | | | 001-099 |
| 0006 | 24 | GK | | 3-0 | 34-22-34 | D41605J | 6 | | | D00085D | H09 | | | 115-199 |
| 0007 | 24 | GK | | 3-1 | 34-22-35 | D00085A | A09 | | | D41567J | 34 | | | 001-099 |
| 0007 | 24 | GK | | 3-0 | 34-22-35 | D41567J | 34 | | | D00085A | A09 | | | 115-199 |
| 0008 | 24 | GK | | 3-1 | SPARE | D00085A | B09 | | | D41567J | 35 | | | 001-099 |
| 0008 | 24 | GK | | 3-0 | 34-22-35 | D41567J | 35 | | | D00085A | B09 | | | 115-199 |
| 0009 | 24 | GK | | 3-1 | 34-22-35 | D00085A | C09 | | | D41567J | 36 | | | 001-099 |
| 0009 | 24 | GK | | 3-0 | 34-22-35 | D41567J | 36 | | | D00085A | C09 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 99

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | | 286N1175 | | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | |
| 0010 | 24 | GK | | | 3-1 | 34-22-35 | D00085A | F09 | | | D41567J | 31 | | | 001-099 |
| 0010 | 24 | GK | | | 3-0 | 34-22-35 | D41567J | 31 | | | D00085A | F09 | | | 115-199 |
| 0011 | 24 | GK | | | 3-1 | 34-22-35 | D00085A | G09 | | | D41567J | 32 | | | 001-099 |
| 0011 | 24 | GK | | | 3-0 | 34-22-35 | D41567J | 32 | | | D00085A | G09 | | | 115-199 |
| 0012 | 24 | GK | | | 3-1 | 34-22-35 | D00085A | H09 | | | D41567J | 33 | | | 001-099 |
| 0012 | 24 | GK | | | 3-0 | 34-22-35 | D41567J | 33 | | | D00085A | H09 | | | 115-199 |
| 0013 | 24 | GK | | | 2-10 | 34-22-36 | D00085C | 1 | | | D40674J | 9 | | | 001-099 |
| 0013 | 24 | GK | | | 3-0 | 34-22-36 | D40674J | 9 | | | D00085C | 1 | | | 115-199 |
| 0014 | 20 | GA | | | 2-5 | 34-22-36 | D00085C | 4 | | | GD02112 | AC.. | 2 | | 001-099 |
| 0014 | 20 | GA | | | 3-0 | 34-22-36 | GD02112 | AC.. | 2 | | D00085C | 4 | | | 115-199 |
| 0015 | 20 | GA | | | 2-5 | 34-22-36 | D00085C | 6 | | | GD02112 | ST.. | 2 | | 001-099 |
| 0015 | 20 | GA | | | 3-0 | 34-22-36 | GD02112 | ST.. | 2 | | D00085C | 6 | | | 115-199 |
| 0016 | 24 | GK | | | 3-4 | 34-22-37 | D00085A | G12 | | | D42049J | 19 | | | 001-099 |
| 0016 | 24 | GK | | | 3-0 | 34-22-37 | SM00073 | | 9 | | D00085A | G12 | | | 115-199 |
| 0017 | 24 | GK | | | 3-9 | 34-22-37 | D00085D | J12 | | | D41605J | 16 | | | 001-099 |
| 0017 | 24 | GK | | | 3-0 | 34-22-37 | D41605J | 16 | | | D00085D | J12 | | | 115-199 |
| 0018 | 24 | GK | | | 3-9 | 34-22-37 | D00085D | E11 | | | D41605J | 17 | | | 001-099 |
| 0018 | 24 | GK | | | 3-0 | 34-22-37 | D41605J | 17 | | | D00085D | E11 | | | 115-199 |
| 0019 | 24 | GK | | | 3-9 | 34-22-37 | D00085D | K12 | | | D41605J | 18 | | | 001-099 |
| 0019 | 24 | GK | | | 3-0 | 34-22-37 | D41605J | 18 | | | D00085D | K12 | | | 115-199 |
| 0020 | 24 | GK | | | 3-9 | 34-22-37 | D00085D | G11 | | | D41605J | 19 | | | 001-099 |
| 0020 | 24 | GK | | | 3-0 | 34-22-37 | D41605J | 19 | | | D00085D | G11 | | | 115-199 |
| 0021 | 22 | GA | | | 2-8 | 34-22-37 | D00085D | J11 | | | GD02112 | ST.. | 2 | | 001-099 |
| 0021 | 22 | GA | | | 3-0 | 34-22-37 | GD02112 | ST.. | 2 | | D00085D | J11 | | | 115-199 |
| 0022 | 22 | GA | | | 2-8 | 34-22-37 | D00085D | A12 | | | GD02112 | ST.. | 2 | | 001-099 |
| 0022 | 22 | GA | | | 3-0 | 34-22-37 | GD02112 | ST.. | 2 | | D00085D | A12 | | | 115-199 |
| 0023 | 22 | GA | | | 3-9 | 34-22-37 | D00085D | A11 | | | D41605J | 38 | | | 001-099 |
| 0023 | 22 | GA | | | 3-0 | 34-22-37 | D41605J | 38 | | | D00085D | A11 | | | 115-199 |
| 0024 | 22 | GA | | | 2-8 | 34-22-37 | D00085D | C11 | | | GD02112 | ST.. | 2 | | 001-099 |
| 0024 | 22 | GA | | | 3-0 | 34-22-37 | GD02112 | ST.. | 2 | | D00085D | C11 | | | 115-199 |
| 0025 | 24 | GK | | | 3-4 | 34-22-37 | D00085A | F12 | | | D42049J | 22 | | | 001-099 |
| 0025 | 24 | GK | | | 3-0 | 34-22-37 | D42049J | 22 | | | D00085A | F12 | | | 115-199 |
| 0026 | 24 | GK | | | 3-9 | 34-22-37 | D00085A | J12 | | | D41605J | 20 | | | 001-099 |
| 0026 | 24 | GK | | | 3-0 | 34-22-37 | D41605J | 20 | | | D00085A | J12 | | | 115-199 |
| 0027 | 24 | GK | | | 3-9 | 34-22-37 | D00085A | K12 | | | D41605J | 21 | | | 001-099 |
| 0027 | 24 | GK | | | 3-0 | 34-22-37 | D41605J | 21 | | | D00085A | K12 | | | 115-199 |
| 0028 | 24 | GK | | | 3-9 | 34-22-37 | D00085A | E11 | | | D41605J | 22 | | | 001-099 |
| 0028 | 24 | GK | | | 3-0 | 34-22-37 | D41605J | 22 | | | D00085A | E11 | | | 115-199 |
| 0029 | 24 | GK | | | 3-9 | 34-22-37 | D00085A | G11 | | | D41605J | 23 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 100

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|-------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0029 | 24 | | GK | | 3-0 | 34-22-37 | D41605J | 23 | | | D00085A | G11 | | | 115-199 |
| 0030 | 20 | | GA | | 1-6 | 34-22-39 | D41567J | | | DB | GD02116 | ST.. | 2 | | ALL |
| 0031 | 20 | | GA | | 1-6 | 34-22-39 | D41567J | | | DC | GD02116 | ST.. | 2 | | ALL |
| 0032 | 20 | | GA | | 1-6 | 34-22-39 | D41567J | | | DD | GD02116 | ST.. | 2 | | ALL |
| 0033 | 24 | | GK | | 2-5 | 34-24-11 | D00447C | 1 | | | D41884J | 9 | | | 001-099 |
| 0033 | 24 | | GK | | 2-0 | 34-24-11 | D41884J | 9 | | | D00447C | 1 | | | 115-199 |
| 0034 | 20 | | GA | | 2-5 | 34-24-11 | D00447C | 5 | | | D41884J | 8 | | | 001-099 |
| 0034 | 20 | | GA | | 2-0 | 34-24-11 | D41884J | 8 | | | D00447C | 5 | | | 115-199 |
| 0035 | 20 | | GA | | 2-3 | 34-24-11 | D00447C | 4 | | | GD02102 | DC.. | 2 | | 001-010 |
| 0035 | 20 | | GA | | 2-0 | 34-24-11 | D00447C | 4 | | | GD02102 | DC.. | 2 | | 011-099 |
| 0035 | 20 | | GA | | 2-0 | 34-24-11 | GD02102 | DC.. | 2 | | D00447C | 4 | | | 115-199 |
| 0036 | 20 | | GA | | 2-3 | 34-24-11 | D00447C | 6 | | | GD02102 | DC.. | 2 | | 001-010 |
| 0036 | 20 | | GA | | 2-0 | 34-24-11 | D00447C | 6 | | | GD02102 | DC.. | 2 | | 011-099 |
| 0036 | 20 | | GA | | 2-0 | 34-24-11 | GD02102 | DC.. | 2 | | D00447C | 6 | | | 115-199 |
| 0037 | 20 | | GA | | 2-3 | 34-24-11 | D00447C | 2 | | | GD02102 | ST.. | 2 | | 001-099 |
| 0037 | 20 | | GA | | 2-0 | 34-24-11 | GD02102 | ST.. | 2 | | D00447C | 2 | | | 115-199 |
| 0038 | 22 | | GA | | 2-6 | 34-31-31 | D00207C | 2 | | | D41884J | 7 | | | 001-099 |
| 0038 | 22 | | GA | | 3-0 | 34-31-31 | D41884J | 7 | | | D02943C | 9 | | | 115-199 |
| 0039 | 20 | | GA | | 2-0 | 34-31-31 | D00207C | 3 | | | GD02102 | AC.. | 2 | | 001-099 |
| 0039 | 20 | | GA | | 2-0 | 34-31-31 | GD02102 | AC.. | 2 | | D02943C | 7 | | | 115-199 |
| 003CO | | | | AH | 0-0 | 34-31-31 | D42139J | = C1 | | | D00207C | = C5 | | | 001-099 |
| 003CO | | | | AU | 0-0 | 34-31-31 | D42139J | = C1 | | | D02943C | = C13 | | | 115-199 |
| 003CX | | 94 | | AH | 2-3 | 34-31-31 | D42139J | = A1 | | | D00207C | 5 | | | 001-099 |
| 003CX | | 94 | | AU | 2-2 | 34-31-31 | D42139J | = A1 | | | D02943C | 13 | | | 115-199 |
| 0040 | 20 | | GA | | 2-5 | 34-31-31 | D00207C | 4 | | | GD02102 | ST.. | 2 | | 001-099 |
| 0040 | 20 | | GA | | 2-0 | 34-31-31 | GD02102 | ST.. | 2 | | D02943C | 8 | | | 115-199 |
| 0041 | 24 | | GK | | 3-2 | 34-31-31 | D41395J | 50 | | | SM00005 | | WI | | 001-099 |
| 0041 | 24 | | GK | | 3-0 | 34-31-31 | D41395J | 50 | | | SM00005 | | WI | | 115-199 |
| 0042 | 24 | | GK | | 3-2 | 34-31-31 | D00207B | D15 | | | SM00005 | | WI | | 001-099 |
| 0042 | 24 | | GK | | 2-0 | 34-31-31 | D02943B | A04 | | | SM00005 | | WI | | 115-199 |
| 0043 | 22 | | GA | | 0-7 | 34-31-31 | D00207B | B03 | | | D00207B | C03 | | | 001-099 |
| 0044 | 22 | | GA | | 0-7 | 34-31-31 | D00207B | B05 | | | D00207B | C05 | | | 001-099 |
| 0045 | 22 | | GA | | 2-9 | 34-31-31 | D42109J | 5 | | | SM00004 | | WI | | 001-099 |
| 0045 | 22 | | GA | | 2-0 | 34-31-31 | D42109J | 5 | | | SM00004 | | WI | | 115-199 |
| 0046 | 22 | | GA | | 4-6 | 34-31-31 | D00085A | E12 | | | D42109J | 11 | | | 001-099 |
| 0046 | 22 | | GA | | 4-0 | 34-31-31 | D42109J | 11 | | | D00085A | E12 | | | 115-199 |
| 0047 | 20 | | GA | | 1-6 | 34-31-31 | D42109J | | | GN | GD02102 | ST.. | 2 | | ALL |
| 0048 | 24 | | GK | | 3-2 | 34-33-31 | D41395J | 51 | | | SM00005 | | WI | | 001-099 |
| 0048 | 24 | | GK | | 3-0 | 34-33-31 | D41395J | 51 | | | SM00005 | | WI | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 101

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|------------|-------------|-------------------------------------|---------------|------------------------|------------------------------------|
| Wire No. | GA CO TY | Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice Effectivity |
| W1175 | 286N1175 | E2-3 INTEGRATION BUNDLE (continued) | | | |
| 004CO | | AB | 0-0 34-31-31 | D42137J = C1 | D00207C = C1 001-099 |
| 004CO | | FH | 0-0 34-31-31 | D42137J = C1 | D02943C = C12 115-199 |
| 004CX | 94 | AB | 2-3 34-31-31 | D42137J = A1 | D00207C 1 001-099 |
| 004CX | 94 | FH | 2-0 34-31-31 | D42137J = A1 | D02943C 12 115-199 |
| 0050 | 22 | GA | 4-8 22-14-11 | D41567J 46 | SM00003 WI 001-099 |
| 0050 | 22 | GA | 4-0 22-14-11 | D41567J 46 | SM00003 WI 115-199 |
| 0051 | 22 | GA | 3-3 22-14-11 | D42049J 35 | SM00003 WI 001-099 |
| 0051 | 22 | GA | 3-0 22-14-11 | D42049J 35 | SM00003 WI 115-199 |
| 0055 | 20 | GA | 1-6 34-22-34 | D41605J | GD02106 ST.. 2 ALL |
| 0056 | 24 | GK | 2-11 31-51-21 | D41097J 37 | SM00006 WI 001, 003-099 |
| 0056 | 22 | GK | 5-0 31-51-21 | D41097J 37 | TB0205Z 116 BJ 002 |
| 0056 | 24 | GK | 2-0 31-51-21 | SM00006 | D41097J 37 115-199 |
| 0057 | 22 | GA | 2-7 34-22-36 | D00085B F09 | GD02112 ST.. 2 001-099 |
| 0057 | 22 | GA | 3-0 34-22-36 | D00085B F09 | GD02112 ST.. # 115-199 |
| 0058 | 22 | GA | 2-5 34-22-36 | D00085B E10 | GD02113 ST.. 2 001-099 |
| 0058 | 22 | GA | 2-0 34-22-36 | D00085B E10 | GD02113 ST.. 2 115-199 |
| 0059 | 20 | GA | 1-6 34-22-35 | D41567J | GD02116 ST.. 2 ALL |
| 005CO | | JH | 0-0 34-31-11 | D42125J = C1 | D00203C = C5 001-099 |
| 005CO | | JH | 0-0 34-31-11 | D42125J = C1 | D02939C = C13 115-199 |
| 005CX | 94 | JH | 1-5 34-31-11 | D42125J = A1 | D00203C 5 001-099 |
| 005CX | 94 | JH | 1-5 34-31-11 | D42125J = A1 | D02939C 13 115-199 |
| 0060 | 20 | GA | 1-6 34-22-38 | D41567J | GD02116 ST.. 2 ALL |
| 0062 | 20 | GA | 1-6 34-22-38 | D41605J | GD02106 ST.. 2 001-099 |
| 0062 | 20 | GA | 1-6 34-22-38 | D41815J | GD02106 ST.. 2 115-199 |
| 0063 | 20 | GA | 1-6 34-22-38 | D41567J | GD02116 ST.. 2 001-099 |
| 0063 | 20 | PA | 1-6 34-22-38 | GD02102 ST.. 2 | D41643J CU 115-199 |
| 0064 | 20 | GA | 1-6 34-22-39 | D41395J | GD02109 ST.. 2 ALL |
| 0065 | 20 | GA | 1-6 34-22-39 | D41605J | GD02106 ST.. 2 ALL |
| 0066 | 20 | GA | 1-6 34-22-39 | D41605J | GD02106 ST.. 2 ALL |
| 0067 | 20 | GA | 1-6 34-22-39 | D41605J | GD02106 ST.. 2 ALL |
| 006CO | | JI | 0-0 34-31-11 | D42121J = C1 | D00203C = C1 001-099 |
| 006CO | | JI | 0-0 34-31-11 | D42121J = C1 | D02939C = C12 115-199 |
| 006CX | 94 | JI | 1-5 34-31-11 | D42121J = A1 | D00203C 1 001-099 |
| 006CX | 94 | JI | 1-5 34-31-11 | D42121J = A1 | D02939C 12 115-199 |
| 0073 | 22 | GA | 4-8 22-34-11 | D00383B D13 | SM00007 WI 001-099 |
| 0073 | 22 | GA | 4-0 22-34-11 | D00383B D13 | SM00007 WI 115-199 |
| 0074 | 22 | GA | 4-8 22-34-11 | D00383B B03 | SM00007 WI 001-099 |
| 0074 | 22 | GA | 4-0 22-34-11 | D00383B B03 | SM00007 WI 115-199 |
| 0075 | 22 | GA | 3-10 22-34-11 | D42021J 5 | SM00007 WI 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 102

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0075 | 22 | | GA | | 4-0 | 22-34-11 | D42021J | | 5 | | SM00007 | | WI | | 115-199 |
| 0076 | 22 | | GA | | 4-8 | 22-34-11 | D00383B | | D09 | | SM00008 | | WI | | 001-099 |
| 0076 | 22 | | GA | | 4-0 | 22-34-11 | D00383B | | D09 | | SM00008 | | WI | | 115-199 |
| 0077 | 22 | | GA | | 4-8 | 22-34-11 | D00383B | | D08 | | SM00008 | | WI | | 001-099 |
| 0077 | 22 | | GA | | 4-0 | 22-34-11 | D00383B | | D08 | | SM00008 | | WI | | 115-199 |
| 0078 | 22 | | GA | | 2-11 | 22-34-11 | D41097J | | 36 | | SM00008 | | WI | | 001-099 |
| 0078 | 22 | | GA | | 2-0 | 22-34-11 | SM00008 | | | WI | D41097J | 36 | | | 115-199 |
| 0079 | 24 | | GK | | 2-6 | 22-32-15 | D00383B | | F05 | | D41711J | 2 | | | 001-099 |
| 0079 | 24 | | GK | | 2-0 | 22-32-15 | D41711J | | 2 | | D00383B | F05 | | | 115-199 |
| 007CO | | | | II | 0-0 | 34-58-11 | D02939A | | = C2 | | D45017J | = C1 | | | 115-199 |
| 007CX | | | 0F | II | 5-0 | 34-58-11 | D02939A | | 2 | | D45017J | = A1 | | | 115-199 |
| 0080 | 20 | | GA | | 2-7 | 22-32-15 | D41711J | | 4 | | GD02113 | DC.. | 2 | | 001-099 |
| 0080 | 20 | | GA | | 3-0 | 22-32-15 | D41711J | | 25 | | GD02113 | DC.. | 2 | | 115-199 |
| 0081 | 24 | | GK | | 2-7 | 22-32-15 | D00383A | | G15 | | D41711J | 1 | | | 001-099 |
| 0081 | 24 | | GK | | 2-0 | 22-32-15 | D41711J | | 1 | | D00383A | G15 | | | 115-199 |
| 0082 | 20 | | GA | | 2-7 | 22-32-15 | D41711J | | 6 | | GD02113 | DC.. | 2 | | 001-099 |
| 0082 | 20 | | GA | | 3-0 | 22-32-15 | D41711J | | 6 | | GD02113 | DC.. | 2 | | 115-199 |
| 0083 | 24 | | GK | | 2-6 | 22-32-15 | D00383B | | E13 | | D41711J | 5 | | | 001-099 |
| 0083 | 24 | | GK | | 2-0 | 22-32-15 | D41711J | | 5 | | D00383B | E13 | | | 115-199 |
| 0084 | 24 | | GK | | 2-7 | 22-32-15 | D00383B | | F01 | | D41567J | 50 | | | 001-099 |
| 0084 | 24 | | GK | | 2-0 | 22-32-15 | D41567J | | 50 | | D00383B | F01 | | | 115-199 |
| 0085 | 24 | | GK | | 4-7 | 22-32-15 | D41711J | | 3 | | SM00011 | | WI | | 001-099 |
| 0085 | 24 | | GK | | 4-0 | 22-32-15 | D41711J | | 3 | | SM00011 | | WI | | 115-199 |
| 0086 | 24 | | GK | | 4-9 | 22-32-15 | D00383A | | K06 | | SM00011 | | WI | | 001-099 |
| 0086 | 24 | | GK | | 4-0 | 22-32-15 | D00383A | | K06 | | SM00011 | | WI | | 115-199 |
| 0087 | 24 | | GK | | 2-5 | 22-32-15 | D42021J | | 3 | | TB0205Y | C087 | BJ | | 001-099 |
| 0087 | 24 | | GK | | 2-0 | 22-32-15 | D42021J | | 3 | | TB0205Y | C087 | BJ | | 115-199 |
| 0088 | 24 | | GK | | 3-5 | 22-32-15 | D00383C | | 1 | | D42021J | 2 | | | 001-099 |
| 0088 | 24 | | GK | | 4-0 | 22-32-15 | D42021J | | 2 | | D00383C | 1 | | | 115-199 |
| 0089 | 20 | | GA | | 3-9 | 22-32-15 | D41097J | | 19 | | GD02113 | DC.. | 2 | | 001-099 |
| 0089 | 20 | | GA | | 4-0 | 22-32-15 | D41097J | | 19 | | GD02113 | DC.. | 2 | | 115-199 |
| 0090 | 24 | | GK | | 4-3 | 22-32-15 | D00383B | | C07 | | D41097J | 20 | | | 001-099 |
| 0090 | 24 | | GK | | 4-0 | 22-32-15 | D41097J | | 20 | | D00383B | C07 | | | 115-199 |
| 0091 | 22 | | GA | | 4-9 | 22-32-14 | D00383A | | D12 | | GD02104 | DC.. | 2 | | 001-099 |
| 0091 | 22 | | GA | | 5-0 | 22-32-14 | D00383A | | D12 | | GD02104 | DC.. | 2 | | 115-199 |
| 0092 | 22 | | GA | | 4-9 | 22-32-14 | D00383A | | D10 | | GD02104 | DC.. | 2 | | 001-099 |
| 0092 | 22 | | GA | | 5-0 | 22-32-14 | D00383A | | D10 | | GD02104 | DC.. | 2 | | 115-199 |
| 0093 | 22 | | GA | | 4-9 | 22-32-14 | D00383A | | G08 | | GD02104 | DC.. | # | | 001-008, 010-099 |
| 0093 | 22 | | GA | | 4-9 | 22-32-14 | D00383A | | G08 | | GD02104 | DC.. | 2 | | 009 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 103

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0093 | 22 | GA | | 5-0 | 22-32-14 | D00383A | G08 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0094 | 22 | GA | | 4-9 | 22-32-14 | D00383A | D11 | | | | GD02104 | DC.. | 2 | | 001-099 |
| 0095 | 22 | GA | | 4-9 | 22-32-14 | D00383A | C11 | | | | GD02104 | DC.. | 2 | | 001-099 |
| 0095 | 22 | GA | | 5-0 | 22-32-14 | D00383A | C11 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0096 | 22 | GA | | 4-9 | 22-32-14 | D00383A | B11 | | | | GD02104 | DC.. | 2 | | 001-099 |
| 0096 | 22 | GA | | 5-0 | 22-32-14 | D00383A | B11 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0097 | 22 | GA | | 4-9 | 22-32-14 | D00383A | E14 | | | | GD02104 | DC.. | 2 | | 001-099 |
| 0097 | 22 | GA | | 5-0 | 22-32-14 | D00383A | E14 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0098 | 22 | GA | | 4-9 | 22-32-14 | D00383A | K05 | | | | GD02104 | DC.. | 2 | | 001-010 |
| 0098 | 22 | GA | | 5-1 | 22-32-14 | D00383A | K05 | | | | TB0205X | B012 | BJ | | 011-099 |
| 0098 | 22 | GA | | 5-0 | 22-32-14 | D00383A | K05 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0099 | 22 | GA | | 4-9 | 22-32-14 | D00383A | F03 | | | | SM00011 | | WI | | 001-010 |
| 0099 | 22 | GA | | 5-1 | 22-32-14 | D00383A | F03 | | | | TB0205Z | 13 | BJ | | 011-099 |
| 0099 | 22 | GA | | 4-0 | 22-32-14 | D00383A | F03 | | | | SM00011 | | WI | | 115-199 |
| 0100 | 22 | GA | | 4-9 | 22-32-14 | D00383A | H06 | | | | GD02104 | DC.. | 2 | | 001-010 |
| 0100 | 22 | GA | | 5-1 | 22-32-14 | D00383A | H06 | | | | TB0205X | A011 | BJ | | 011-099 |
| 0100 | 22 | GA | | 5-0 | 22-32-14 | D00383A | H06 | | | | SM00011 | | WI | | 115-199 |
| 0101 | 22 | GA | | 4-9 | 22-32-14 | D00383A | J12 | | | | GD02104 | DC.. | 2 | | 001-010 |
| 0101 | 22 | GA | | 5-1 | 22-32-14 | D00383A | J12 | | | | TB0205X | B011 | BJ | | 011-099 |
| 0101 | 22 | GA | | 5-0 | 22-32-14 | D00383A | J12 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0102 | 22 | GA | | 4-9 | 22-32-14 | D00383A | F09 | | | | SM00011 | | WI | | 001-010 |
| 0102 | 22 | GA | | 5-1 | 22-32-14 | D00383A | F09 | | | | TB0205Z | 13 | BJ | | 011-099 |
| 0102 | 22 | GA | | 4-0 | 22-32-14 | D00383A | F09 | | | | SM00011 | | WI | | 115-199 |
| 0103 | 22 | GA | | 4-7 | 22-32-14 | D00383B | H10 | | | | GD02104 | DC.. | 2 | | 001-010 |
| 0103 | 22 | GA | | 5-0 | 22-32-14 | D00383B | H10 | | | | TB0205X | D011 | BJ | | 011-099 |
| 0103 | 22 | GA | | 5-0 | 22-32-14 | D00383B | H10 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0104 | 22 | GA | | 4-9 | 22-32-14 | D00383A | F07 | | | | SM00011 | | WI | | 001-010 |
| 0104 | 22 | GA | | 5-1 | 22-32-14 | D00383A | F07 | | | | TB0205Z | 13 | BJ | | 011-099 |
| 0104 | 22 | GA | | 4-0 | 22-32-14 | D00383A | F07 | | | | SM00011 | | WI | | 115-199 |
| 0105 | 22 | GA | | 4-9 | 22-32-14 | D00383A | D13 | | | | GD02103 | DC.. | # | | 001-099 |
| 0105 | 22 | GA | | 5-0 | 22-32-14 | D00383A | D13 | | | | GD02103 | DC.. | # | | 115-199 |
| 0106 | 22 | GA | | 4-9 | 22-32-14 | D00383A | E15 | | | | GD02104 | DC.. | 2 | | 001-099 |
| 0106 | 22 | GA | | 5-0 | 22-32-14 | D00383A | E15 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0107 | 22 | GA | | 4-7 | 22-32-14 | D00383B | F02 | | | | GD02104 | DC.. | 2 | | 001-099 |
| 0107 | 22 | GA | | 5-0 | 22-32-14 | D00383B | F02 | | | | GD02104 | DC.. | 2 | | 115-199 |
| 0108 | 22 | GA | | 4-7 | 22-32-14 | D00383B | F06 | | | | GD02104 | DC.. | # | | 001-099 |
| 0108 | 22 | GA | | 5-0 | 22-32-14 | D00383B | F06 | | | | GD02104 | DC.. | # | | 115-199 |
| 0109 | 22 | GA | | 4-7 | 22-32-14 | D00383B | G11 | | | | GD02103 | DC.. | 2 | | 001-099 |
| 0109 | 22 | GA | | 5-0 | 22-32-14 | D00383B | G11 | | | | GD02103 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 104

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0110 | 22 | | GA | | 4-7 | 22-32-14 | D00383B | C01 | | | GD02103 | DC.. | 2 | | 001-099 |
| 0110 | 22 | | GA | | 5-0 | 22-32-14 | D00383B | C01 | | | GD02103 | DC.. | 2 | | 115-199 |
| 0111 | 22 | | GA | | 4-7 | 22-32-14 | D00383B | D10 | | | GD02103 | DC.. | # | | 001-099 |
| 0111 | 22 | | GA | | 5-0 | 22-32-14 | D00383B | D10 | | | GD02103 | DC.. | # | | 115-199 |
| 0112 | 20 | | GA | | 2-3 | 22-41-11 | D41815J | | | ER | GD02110 | ST.. | 2 | | 001-099 |
| 0112 | 20 | | GA | | 3-0 | 22-41-11 | GD02110 | ST.. | 2 | | D41815J | | | ER | 115-199 |
| 0113 | 24 | | GK | | 4-8 | 22-32-13 | D00383B | H09 | | | SM00011 | | WI | | 001-099 |
| 0113 | 24 | | GK | | 4-0 | 22-32-13 | D00383B | H09 | | | SM00011 | | WI | | 115-199 |
| 0114 | 24 | | GK | | 4-3 | 22-32-13 | D00383B | H02 | | | D41097J | | 7 | | 001-099 |
| 0114 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383B | | H02 | | 115-199 |
| 0115 | 24 | | GK | | 4-4 | 22-32-13 | D00383A | F05 | | | D41097J | | 8 | | 001-099 |
| 0115 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383A | | F05 | | 115-199 |
| 0116 | 24 | | GK | | 4-4 | 22-32-13 | D00383A | F04 | | | D41097J | | 9 | | 001-099 |
| 0116 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383A | | F04 | | 115-199 |
| 0117 | 24 | | GK | | 4-4 | 22-32-13 | D00383A | K02 | | | D41097J | | 10 | | 001-099 |
| 0117 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383A | | K02 | | 115-199 |
| 0118 | 24 | | GK | | 2-8 | 22-32-13 | D00383A | G11 | | | TB0205Y | A094 | BJ | | 001-099 |
| 0118 | 24 | | GK | | 2-0 | 22-32-13 | TB0205Y | A094 | BJ | | D00383A | | G11 | | 115-199 |
| 0119 | 24 | | GK | | 2-8 | 22-32-13 | D00383A | E03 | | | TB0205Y | A093 | BJ | | 001-099 |
| 0119 | 24 | | GK | | 2-0 | 22-32-13 | TB0205Y | A093 | BJ | | D00383A | | E03 | | 115-199 |
| 0120 | 24 | | GK | | 2-8 | 22-32-13 | D00383A | G04 | | | TB0205Y | C094 | BJ | | 001-099 |
| 0120 | 24 | | GK | | 3-0 | 22-32-13 | TB0205Y | C094 | BJ | | D00383A | | G04 | | 115-199 |
| 0121 | 24 | | GK | | 4-4 | 22-32-13 | D00383A | J03 | | | D41097J | | 11 | | 001-099 |
| 0121 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383A | | J03 | | 115-199 |
| 0122 | 24 | | GK | | 4-3 | 22-32-13 | D00383B | H08 | | | D41097J | | 12 | | 001-099 |
| 0122 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383B | | H08 | | 115-199 |
| 0123 | 24 | | GK | | 4-4 | 22-32-13 | D00383A | K10 | | | D41097J | | 13 | | 001-099 |
| 0123 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383A | | K10 | | 115-199 |
| 0124 | 24 | | GK | | 4-3 | 22-32-13 | D00383B | D05 | | | D41097J | | 14 | | 001-099 |
| 0124 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383B | | D05 | | 115-199 |
| 0125 | 24 | | GK | | 4-3 | 22-32-13 | D00383B | D06 | | | D41097J | | 15 | | 001-099 |
| 0125 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383B | | D06 | | 115-199 |
| 0126 | 24 | | GK | | 4-3 | 22-32-13 | D00383B | G02 | | | D41097J | | 16 | | 001-099 |
| 0126 | 24 | | GK | | 4-0 | 22-32-13 | D41097J | | | | D00383B | | G02 | | 115-199 |
| 0127 | 24 | | GK | | 2-7 | 22-32-13 | D00383B | D04 | | | TB0205Y | C093 | BJ | | 001-099 |
| 0127 | 24 | | GK | | 4-0 | 22-32-13 | TB0205Y | C093 | BJ | | D00383B | | D04 | | 115-199 |
| 0128 | 22 | | GA | | 2-5 | 22-32-13 | D00383B | E10 | | | GD02116 | ST.. | 2 | | 001-099 |
| 0128 | 22 | | GA | | 2-0 | 22-32-13 | GD02116 | ST.. | 2 | | D00383B | | E10 | | 115-199 |
| 0129 | 22 | | GA | | 2-5 | 22-32-13 | D00383B | J01 | | | GD02116 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 105

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0129 | 22 | | GA | | 2-0 | 22-32-13 | GD02116 | ST.. | 2 | | D00383B | J01 | | | 115-199 |
| 0130 | 22 | | GA | | 2-5 | 22-32-13 | D00383B | E02 | | | GD02116 | ST.. | 2 | | 001-099 |
| 0130 | 22 | | GA | | 2-0 | 22-32-13 | GD02116 | ST.. | 2 | | D00383B | E02 | | | 115-199 |
| 0131 | 20 | | GA | | 1-6 | 22-32-11 | D42063J | | | AO | GD02112 | ST.. | 2 | | ALL |
| 0132 | 20 | | GA | | 1-6 | 22-32-11 | D41819J | | | AP | GD02116 | ST.. | 2 | | ALL |
| 0133 | 20 | | GA | | 1-6 | 22-32-11 | D41819J | | | AQ | GD02116 | ST.. | 2 | | ALL |
| 0134 | 20 | | GA | | 1-6 | 22-32-11 | D41823J | | | AV | GD02112 | ST.. | 2 | | ALL |
| 0135 | 20 | | GA | | 1-6 | 22-32-11 | D41823J | | | AW | GD02112 | ST.. | 2 | | ALL |
| 0136 | 20 | | GA | | 3-5 | 22-31-12 | D00383C | | 2 | | D40674J | 11 | | | 001-099 |
| 0136 | 20 | | GA | | 4-0 | 22-31-12 | D40674J | | 15 | | D00383C | 2 | | | 115-199 |
| 0137 | 20 | | GA | | 3-5 | 22-31-12 | D00383C | | 9 | | D40674J | 10 | | | 001-099 |
| 0137 | 20 | | GA | | 4-0 | 22-31-12 | D40674J | | 14 | | D00383C | 9 | | | 115-199 |
| 0138 | 22 | | GA | | 4-9 | 22-32-14 | D00383A | H15 | | | GD02104 | DC.. | 2 | | 001-099 |
| 0138 | 22 | | GA | | 5-0 | 22-32-14 | D00383A | H15 | | | GD02104 | DC.. | # | | 115-199 |
| 0140 | 20 | | GA | | 2-6 | 22-31-12 | D00383C | | 7 | | GD02113 | DC.. | 2 | | 001-099 |
| 0140 | 20 | | GA | | 3-0 | 22-31-12 | D00383C | | 7 | | GD02113 | DC.. | 2 | | 115-199 |
| 0141 | 22 | | GA | | 2-9 | 22-31-12 | D00383A | K03 | | | GD02113 | DC.. | 2 | | 001-099 |
| 0141 | 22 | | GA | | 3-0 | 22-31-12 | D00383A | K03 | | | GD02113 | DC.. | 2 | | 115-199 |
| 0142 | 20 | | GA | | 4-7 | 22-31-11 | D00383C | | 10 | | SM00012 | | WI | | 001-099 |
| 0142 | 20 | | GA | | 4-0 | 22-31-11 | D00383C | | 10 | | SM00012 | | WI | | 115-199 |
| 0143 | 20 | | GA | | 3-10 | 22-31-11 | D40674J | | 6 | | SM00012 | | WI | | 001-099 |
| 0143 | 20 | | GA | | 4-0 | 22-31-11 | D40674J | | 6 | | SM00012 | | WI | | 115-199 |
| 0145 | 24 | | GK | | 4-7 | 22-31-11 | D41711J | | 7 | | SM00012 | | WI | | 001-099 |
| 0145 | 24 | | GK | | 4-0 | 22-31-11 | D41711J | | 7 | | SM00012 | | WI | | 115-199 |
| 0147 | 20 | | GA | | 2-4 | 22-31-11 | D00383C | | 6 | | D41711J | 8 | | | 001-099 |
| 0147 | 20 | | GA | | 2-0 | 22-31-11 | D41711J | | 8 | | D00383C | 6 | | | 115-199 |
| 0148 | 20 | | GA | | 4-6 | 22-31-11 | GD02115 | AC.. | 2 | | SM00010 | | WI | | 001-099 |
| 0148 | 20 | | GA | | 4-0 | 22-31-11 | SM00010 | | WI | | GD02115 | AC.. | 2 | | 115-199 |
| 0149 | 20 | | GA | | 2-3 | 22-31-11 | D00383C | | 8 | | GD02116 | ST.. | 2 | | 001-099 |
| 0149 | 20 | | GA | | 2-0 | 22-31-11 | GD02116 | ST.. | 2 | | D00383C | 8 | | | 115-199 |
| 0150 | 20 | | GA | | 2-3 | 22-31-11 | D00383C | | 3 | | GD02116 | AC.. | 2 | | 001-099 |
| 0150 | 20 | | GA | | 2-0 | 22-31-11 | GD02116 | AC.. | 2 | | D00383C | 3 | | | 115-199 |
| 0157 | 20 | | GA | | 2-1 | 22-11-31 | D00055C | | 6 | | D41890J | 1 | | | 001-099 |
| 0157 | 20 | | GA | | 2-0 | 22-11-31 | D41890J | | 1 | | D00055C | 6 | | | 115-199 |
| 0158 | 20 | | GA | | 2-8 | 22-11-31 | D00055C | | 7 | | GD02111 | ST.. | 2 | | 001-099 |
| 0158 | 20 | | GA | | 3-0 | 22-11-31 | D00055C | | 7 | | GD02111 | ST.. | 2 | | 115-199 |
| 0159 | 20 | | GA | | 2-8 | 22-11-31 | D00055C | | 4 | | GD02111 | AC.. | 2 | | 001-099 |
| 0159 | 20 | | GA | | 3-0 | 22-11-31 | D00055C | | 4 | | GD02111 | AC.. | 2 | | 115-199 |
| 0162 | 20 | | GA | | 3-2 | 22-11-32 | D00055C | | 2 | | SM00016 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 106

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1175 | 286N1175 | | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0162 | 20 | | GA | | 3-0 | 22-11-32 | D00055C | | 2 | | | SM00016 | | WI | | 115-199 | |
| 0163 | 20 | | GA | | 3-0 | 22-11-32 | D41890J | | 3 | | | SM00016 | | WI | | ALL | |
| 0164 | 20 | | GA | | 3-2 | 22-11-32 | D00055C | | 5 | | | SM00016 | | WI | | 001-099 | |
| 0164 | 20 | | GA | | 3-0 | 22-11-32 | SM00016 | | | WI | | D00055C | 5 | | | 115-199 | |
| 0165 | 22 | | GA | | 3-2 | 22-11-32 | D00055C | | 1 | | | SM00016 | | WI | | 001-099 | |
| 0165 | 22 | | GA | | 3-0 | 22-11-32 | SM00016 | | | WI | | D00055C | 1 | | | 115-199 | |
| 0166 | 22 | | GA | | 3-5 | 22-11-32 | D00055A | | H15 | | | SM00017 | | WI | | 001-099 | |
| 0166 | 22 | | GA | | 3-0 | 22-11-32 | D00055A | | H15 | | | SM00017 | | WI | | 115-199 | |
| 0167 | 22 | | GA | | 3-3 | 22-11-32 | D42049J | | 15 | | | SM00016 | | WI | | 001-099 | |
| 0167 | 22 | | GA | | 3-0 | 22-11-32 | D42049J | | 15 | | | SM00016 | | WI | | 115-199 | |
| 0168 | 22 | | GA | | 3-3 | 22-11-32 | D42049J | | 16 | | | SM00017 | | WI | | 001-099 | |
| 0168 | 22 | | GA | | 3-0 | 22-11-32 | D42049J | | 16 | | | SM00017 | | WI | | 115-199 | |
| 0169 | 22 | | GA | | 3-3 | 22-11-32 | D00055B | | H15 | | | SM00017 | | WI | | 001-099 | |
| 0169 | 22 | | GA | | 3-0 | 22-11-32 | SM00017 | | | WI | | D00055B | H15 | | | 115-199 | |
| 0170 | 22 | | GA | | 2-0 | 22-11-32 | D42049J | | 17 | | | D00055B | G11 | | | 115-199 | |
| 0171 | 22 | | GA | | 1-0 | 22-11-32 | D00055B | | G13 | | | D00055B | H14 | | | 115-199 | |
| 0172 | 22 | | GA | | 3-0 | 22-11-32 | SM00014 | | | WI | | D00055B | A06 | | | 115-199 | |
| 0173 | 22 | | GA | | 4-0 | 22-11-32 | D41888J | | 1 | | | SM00014 | | WI | | 115-199 | |
| 0174 | 22 | | GA | | 4-0 | 22-11-32 | D41888J | | 2 | | | SM00015 | | WI | | 115-199 | |
| 0175 | 22 | | GA | | 3-0 | 22-11-32 | SM00015 | | | WI | | D00055B | C07 | | | 115-199 | |
| 0176 | 22 | | GA | | 0-7 | 22-11-32 | D00055B | | E04 | | | D00055B | A03 | | | 001-008 | |
| 0176 | 22 | | GA | | 2-0 | 22-11-32 | D00055B | | E04 | | | D00055B | A03 | | | 115-199 | |
| 0177 | 22 | | GA | | 3-0 | 22-11-32 | D00055B | | F15 | | | D41705J | 1 | | | 001-099 | |
| 0177 | 22 | | GA | | 3-0 | 22-11-32 | D41705J | | 1 | | | D00055B | F15 | | | 115-199 | |
| 0178 | 22 | | GA | | 0-7 | 22-11-32 | D00055A | | A14 | | | D00055A | A13 | | | 001-008 | |
| 0178 | 22 | | GA | | 0-7 | 22-11-33 | D00055A | | A14 | | | D00055A | A13 | | | 009-099 | |
| 0178 | 22 | | GA | | 1-0 | 22-11-32 | D00055A | | A14 | | | D00055A | A13 | | | 115-199 | |
| 0179 | 22 | | GA | | 0-7 | 22-11-32 | D00055A | | B14 | | | D00055A | B13 | | | 001-008 | |
| 0179 | 22 | | GA | | 0-7 | 22-11-33 | D00055A | | B14 | | | D00055A | B13 | | | 009-099 | |
| 0179 | 22 | | GA | | 2-0 | 22-11-32 | D00055A | | B14 | | | D00055A | B13 | | | 115-199 | |
| 0180 | 22 | | GA | | 2-11 | 22-11-32 | D41705J | | 6 | | | GD02110 | DC.. | 2 | | 001-099 | |
| 0180 | 22 | | GA | | 3-0 | 22-11-32 | GD02110 | | DC.. | 2 | | D41705J | 6 | | | 115-199 | |
| 0181 | 22 | | GA | | 3-1 | 22-11-32 | D00055A | | K15 | | | D41695J | 19 | | | 001-099 | |
| 0181 | 22 | | GA | | 3-0 | 22-11-32 | D00055A | | K15 | | | D41695J | 19 | | | 115-199 | |
| 0182 | 22 | | GA | | 3-0 | 22-11-32 | D00055B | | K15 | | | D41695J | 14 | | | ALL | |
| 0183 | 22 | | GA | | 3-0 | 22-11-32 | D00055B | | A15 | | | D41695J | 1 | | | ALL | |
| 0184 | 22 | | GA | | 3-1 | 22-11-32 | D00055A | | A15 | | | D41695J | 17 | | | 001-099 | |
| 0184 | 22 | | GA | | 3-0 | 22-11-32 | D00055A | | A15 | | | D41695J | 17 | | | 115-199 | |
| 0185 | 22 | | GA | | 2-6 | 22-11-32 | D00055A | | A04 | | | GD02110 | DC.. | 2 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 107

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0185 | 22 | | GA | | 2-0 | 22-11-32 | D00055A | A04 | | | | GD02110 | DC.. | 2 | | 115-199 |
| 0186 | 22 | | GA | | 2-6 | 22-11-32 | D00055A | G11 | | | | GD02110 | DC.. | 2 | | 001-099 |
| 0186 | 22 | | GA | | 2-0 | 22-11-32 | D00055A | G11 | | | | GD02110 | DC.. | 2 | | 115-199 |
| 0188 | 22 | | GA | | 0-7 | 22-11-32 | D00055A | A12 | | | | D00055A | A11 | | | 001-008 |
| 0188 | 22 | | GA | | 0-7 | 22-11-33 | D00055A | A12 | | | | D00055A | A11 | | | 009-099 |
| 0188 | 22 | | GA | | 2-0 | 22-11-32 | D00055A | A12 | | | | D00055A | A11 | | | 115-199 |
| 0189 | 22 | | GA | | 2-11 | 22-11-32 | D00055A | C15 | | | | D41622J | 24 | | | 001-099 |
| 0189 | 22 | | GA | | 4-0 | 22-11-32 | D00055A | C15 | | | | D41622J | 24 | | | 115-199 |
| 0190 | 22 | | GA | | 2-10 | 22-11-32 | D00055B | C15 | | | | D41622J | 22 | | | 001-099 |
| 0190 | 22 | | GA | | 4-0 | 22-11-32 | D00055B | C15 | | | | D41622J | 22 | | | 115-199 |
| 0191 | 22 | | GA | | 2-4 | 22-11-32 | D00055B | H11 | | | | D41815J | 10 | | | 001-099 |
| 0191 | 22 | | GA | | 2-0 | 22-11-32 | D00055B | H11 | | | | D41815J | 10 | | | 115-199 |
| 0192 | 20 | | GA | | 1-6 | 22-12-11 | D41567J | | | | DL | GD02116 | ST.. | 2 | | ALL |
| 0193 | 20 | | GA | | 1-6 | 22-12-21 | D41605J | | | | DM | GD02106 | ST.. | 2 | | ALL |
| 0194 | 20 | | GA | | 1-6 | 22-12-31 | D41395J | | | | DP | GD02109 | ST.. | 2 | | 001-099 |
| 0194 | 20 | | GA | | 3-0 | 22-12-31 | D41395J | | | | DP | GD02109 | ST.. | 2 | | 115-199 |
| 0195 | 22 | | GA | | 2-5 | 22-12-31 | D00055B | E10 | | | | D41395J | 11 | | | 001-099 |
| 0195 | 22 | | GA | | 2-0 | 22-12-31 | D41395J | 11 | | | | D00055B | E10 | | | 115-199 |
| 0196 | 20 | | GA | | 3-5 | 22-12-31 | D41705J | 7 | | | | GD02112 | DC.. | 2 | | 001-099 |
| 0196 | 20 | | GA | | 4-0 | 22-12-31 | D41705J | 7 | | | | GD02112 | DC.. | 2 | | 115-199 |
| 0197 | 22 | | GA | | 3-1 | 22-12-31 | D00055A | F15 | | | | D41705J | 8 | | | 001-099 |
| 0197 | 22 | | GA | | 3-0 | 22-12-31 | D41705J | 8 | | | | D00055A | F15 | | | 115-199 |
| 0198 | 22 | | GA | | 2-5 | 22-12-31 | D00055B | D08 | | | | D41395J | 18 | | | 001-099 |
| 0198 | 22 | | GA | | 2-0 | 22-12-31 | D00055B | D08 | | | | D41395J | 18 | | | 115-199 |
| 0199 | 22 | | GA | | 2-5 | 22-12-31 | D00055B | C09 | | | | D41395J | 19 | | | 001-099 |
| 0199 | 22 | | GA | | 2-0 | 22-12-31 | D00055B | C09 | | | | D41395J | 19 | | | 115-199 |
| 0200 | 22 | | GA | | 2-5 | 22-12-31 | D00055B | D10 | | | | D41395J | 20 | | | 001-099 |
| 0200 | 22 | | GA | | 2-0 | 22-12-31 | D00055B | D10 | | | | D41395J | 20 | | | 115-199 |
| 0201 | 22 | | GA | | 2-5 | 22-12-31 | D00055B | D09 | | | | D41395J | 21 | | | 001-099 |
| 0201 | 22 | | GA | | 2-0 | 22-12-31 | D00055B | D09 | | | | D41395J | 21 | | | 115-199 |
| 0202 | 22 | | GA | | 2-4 | 22-12-31 | D00055B | G09 | | | | D41815J | 1 | | | 001-099 |
| 0202 | 22 | | GA | | 2-0 | 22-12-31 | D00055B | G09 | | | | D41815J | 1 | | | 115-199 |
| 0203 | 22 | | GA | | 2-5 | 22-12-31 | D00055A | G09 | | | | D41815J | 6 | | | 001-099 |
| 0203 | 22 | | GA | | 2-0 | 22-12-31 | D00055A | G09 | | | | D41815J | 6 | | | 115-199 |
| 0204 | 22 | | GA | | 2-5 | 22-12-31 | D00055A | F12 | | | | D41815J | 2 | | | 001-099 |
| 0204 | 22 | | GA | | 2-0 | 22-12-31 | D00055A | F12 | | | | D41815J | 2 | | | 115-199 |
| 0205 | 20 | | GA | | 1-6 | 22-12-31 | D41643J | | | | DQ | GD02102 | ST.. | 2 | | 001-099 |
| 0205 | 20 | | GA | | 1-6 | 22-12-31 | GD02102 | ST.. | 2 | | | D41643J | | | DQ | 115-199 |
| 0207 | 22 | | GA | | 3-2 | 22-13-31 | D00207B | C01 | | | | SM00004 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 108

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0207 | 22 | | GA | | 2-0 | 22-13-31 | D02943B | F15 | | | SM00004 | | WI | | 115-199 |
| 0208 | 22 | | GA | | 3-3 | 22-13-31 | D00055B | H03 | | | SM00004 | | WI | | 001-099 |
| 0208 | 22 | | GA | | 3-0 | 22-13-31 | D00055B | H03 | | | SM00004 | | WI | | 115-199 |
| 0213 | 22 | | GA | | 2-10 | 22-14-21 | D42167J | 4 | | | SM00003 | | WI | | 001-099 |
| 0213 | 22 | | GA | | 2-0 | 22-14-21 | D42167J | 4 | | | SM00003 | | WI | | 115-199 |
| 0216 | 22 | | GA | | 2-5 | 22-14-31 | D00055B | K11 | | | D41395J | 31 | | | 001-099 |
| 0216 | 22 | | GA | | 2-0 | 22-14-31 | D41395J | 31 | | | D00055B | K11 | | | 115-199 |
| 0217 | 22 | | GA | | 2-5 | 22-14-31 | D00055B | K12 | | | D41395J | 52 | | | 001-099 |
| 0217 | 22 | | GA | | 2-0 | 22-14-31 | D41395J | 52 | | | D00055B | K12 | | | 115-199 |
| 0218 | 22 | | GA | | 2-5 | 22-14-31 | D00055B | K10 | | | D41395J | 32 | | | 001-099 |
| 0218 | 22 | | GA | | 2-0 | 22-14-31 | D41395J | 32 | | | D00055B | K10 | | | 115-199 |
| 0219 | 22 | | GA | | 3-3 | 22-14-31 | D00055B | J12 | | | SM00003 | | WI | | 001-099 |
| 0219 | 22 | | GA | | 3-0 | 22-14-31 | SM00003 | | WI | | D00055B | J12 | | | 115-199 |
| 0220 | 22 | | GA | | 2-5 | 22-14-31 | D00055B | J11 | | | D41395J | 29 | | | 001-099 |
| 0220 | 22 | | GA | | 2-0 | 22-14-31 | D41395J | 29 | | | D00055B | J11 | | | 115-199 |
| 0223 | 22 | | GA | | 2-6 | 22-14-31 | D00055A | G12 | | | D41395J | 35 | | | 001-099 |
| 0223 | 22 | | GA | | 2-0 | 22-14-31 | D41395J | 35 | | | D00055A | G12 | | | 115-199 |
| 0224 | 22 | | GA | | 2-6 | 22-14-31 | D00055A | E12 | | | D41395J | 36 | | | 001-099 |
| 0224 | 22 | | GA | | 2-0 | 22-14-31 | D41395J | 36 | | | D00055A | E12 | | | 115-199 |
| 0228 | 20 | | GA | | 1-6 | 22-15-11 | D41395J | | | EL | GD02109 | ST.. | 2 | | 001-099 |
| 0228 | 20 | | GA | | 3-0 | 22-15-11 | D41395J | | | EL | GD02109 | ST.. | 2 | | 115-199 |
| 0229 | 20 | | GA | | 1-6 | 22-15-11 | D41349J | | | EM | GD02106 | ST.. | 2 | | ALL |
| 0230 | 20 | | GA | | 1-6 | 22-15-11 | D41097J | | | EN | GD02107 | ST.. | 2 | | 001-099 |
| 0230 | 20 | | GA | | 1-6 | 22-15-11 | GD02107 | ST.. | 2 | | D41097J | | | EN | 115-199 |
| 0231 | 20 | | GA | | 1-6 | 22-15-11 | D41395J | | | EO | GD02109 | ST.. | 2 | | 001-099 |
| 0231 | 20 | | GA | | 1-6 | 22-15-11 | GD02109 | ST.. | 2 | | D41395J | | | EO | 115-199 |
| 0232 | 22 | | GA | | 3-5 | 22-15-12 | D00055A | G10 | | | SM00021 | | WI | | 001-099 |
| 0232 | 22 | | GA | | 3-0 | 22-15-12 | D00055A | G10 | | | SM00021 | | WI | | 115-199 |
| 0233 | 22 | | GA | | 3-2 | 22-15-12 | D41395J | 44 | | | SM00021 | | WI | | 001-099 |
| 0233 | 22 | | GA | | 3-0 | 22-15-12 | SM00021 | | WI | | D41395J | 44 | | | 115-199 |
| 0234 | 22 | | GA | | 3-2 | 22-15-12 | D41395J | 45 | | | SM00021 | | WI | | 001-099 |
| 0234 | 22 | | GA | | 3-0 | 22-15-12 | SM00021 | | WI | | D41395J | 45 | | | 115-199 |
| 0237 | 24 | | GK | | 3-4 | 34-46-11 | D00433C | 2 | | | D40674J | 4 | | | 001-099 |
| 0237 | 22 | | GA | | 4-0 | 34-46-11 | D00433C | 2 | | | D40674J | 4 | | | 115-199 |
| 0238 | 20 | | GA | | 2-1 | 34-46-11 | D00433C | 3 | | | GD02106 | AC.. | 2 | | 001-099 |
| 0238 | 20 | | GA | | 2-0 | 34-46-11 | D00433C | 3 | | | GD02106 | AC.. | 2 | | 115-199 |
| 0239 | 20 | | GA | | 2-1 | 34-46-11 | D00433C | 4 | | | GD02106 | DC.. | 2 | | 001-099 |
| 0239 | 20 | | GA | | 2-0 | 34-46-11 | D00433C | 4 | | | GD02106 | DC.. | 2 | | 115-199 |
| 0240 | 24 | | GK | | 4-1 | 34-46-11 | D42083J | 13 | | | SM00023 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 109

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|-------------|------------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 0240 | 24 | | GK | | 4-0 | 34-46-11 | D42083J | 13 | | | | SM00023 | | WI | 115-199 | |
| 0241 | 24 | | GK | | 2-10 | 34-46-11 | D00433B | C09 | | | | SM00023 | | WI | 001-099 | |
| 0241 | 24 | | GK | | 2-0 | 34-46-11 | D00433B | C09 | | | | SM00023 | | WI | 115-199 | |
| 0242 | 24 | | GK | | 4-1 | 34-46-11 | D42083J | 14 | | | | SM00022 | | WI | 001-099 | |
| 0242 | 24 | | GK | | 4-0 | 34-46-11 | D42083J | 14 | | | | SM00022 | | WI | 115-199 | |
| 0243 | 24 | | GK | | 2-10 | 34-46-11 | D00433B | B09 | | | | SM00022 | | WI | 001-099 | |
| 0243 | 24 | | GK | | 2-0 | 34-46-11 | D00433B | B09 | | | | SM00022 | | WI | 115-199 | |
| 0244 | 24 | | GK | | 3-6 | 34-46-11 | D00433B | D09 | | | | D42021J | 8 | | 001-099 | |
| 0244 | 24 | | GK | | 4-0 | 34-46-11 | D00433B | D09 | | | | D42021J | 16 | | 115-199 | |
| 0245 | 22 | | GA | | 3-10 | 34-46-11 | SM00031 | | WI | | | D42021J | 9 | | 001, 003-099 | |
| 0245 | 22 | | GA | | 3-10 | 34-46-11 | TB0205Y | C099 | BJ | | | D42021J | 9 | | 002 | |
| 0245 | 22 | | GA | | 4-0 | 34-46-11 | SM00031 | | WI | | | D42021J | 17 | | 115-199 | |
| 0246 | 22 | | GA | | 3-10 | 34-46-11 | D42021J | 10 | | | | SM00006 | | WI | 001, 003-099 | |
| 0246 | 22 | | GA | | 3-10 | 34-46-11 | D42021J | 10 | | | | TB0205Z | 116 | BJ | 002 | |
| 0246 | 22 | | GA | | 4-0 | 34-46-11 | D42021J | 18 | | | | SM00006 | | WI | 115-199 | |
| 0247 | 22 | | GA | | 2-10 | 34-46-11 | D00433B | B07 | | | | SM00006 | | WI | 001, 003-099 | |
| 0247 | 22 | | GA | | 2-0 | 34-46-11 | D00433B | B07 | | | | SM00006 | | WI | 115-199 | |
| 0248 | 24 | | GK | | 2-6 | 34-46-11 | D00433B | A09 | | | | D41097J | 49 | | 001-099 | |
| 0248 | 24 | | GK | | 2-0 | 34-46-11 | D00433B | A09 | | | | D41097J | 49 | | 115-199 | |
| 0249 | 24 | | GK | | 2-8 | 34-46-12 | D00433B | A01 | | | | D41433J | 45 | | 001-099 | |
| 0249 | 24 | | GK | | 3-0 | 34-46-12 | D00433B | A01 | | | | D41433J | 45 | | 115-199 | |
| 0250 | 24 | | GK | | 2-5 | 34-46-12 | D41433J | 2 | | | | SM00022 | | WI | 001-099 | |
| 0250 | 24 | | GK | | 2-0 | 34-46-12 | D41433J | 2 | | | | SM00022 | | WI | 115-199 | |
| 0251 | 24 | | GK | | 2-5 | 34-46-12 | D41433J | 3 | | | | SM00023 | | WI | 001-099 | |
| 0251 | 24 | | GK | | 2-0 | 34-46-12 | D41433J | 3 | | | | SM00023 | | WI | 115-199 | |
| 0252 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | | AC | GD02103 | ST.. | 2 | *3 | 001-099 |
| 0252 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | | AC | GD02103 | ST.. | 2 | | 115-199 |
| 0253 | 20 | | GA | | 1-6 | 34-46-12 | D41349J | | | | AD | GD02106 | ST.. | 2 | | 001-008, 010-099 |
| 0254 | 24 | | GK | | 2-8 | 34-46-12 | D00433B | CAP | Y | | | D41433J | 7 | | 001, 003-099 | |
| 0254 | 24 | | GK | | 3-0 | 34-46-12 | D41433J | 7 | | | | D00433B | CAP | Y | 115-199 | |
| 0255 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | | AE | GD02103 | ST.. | 2 | *3 | 001-099 |
| 0255 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | | AE | GD02103 | ST.. | 2 | | 115-199 |
| 0256 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | | AF | GD02103 | ST.. | 2 | *4 | 001-099 |
| 0256 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | | AF | GD02103 | ST.. | 2 | | 115-199 |
| 0257 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | | AG | GD02103 | ST.. | 2 | *4 | 001-099 |
| 0257 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | | AG | GD02103 | ST.. | 2 | | 115-199 |
| 0259 | 22 | | GA | | 4-0 | 34-46-12 | D00433B | C07 | | | | TB0205Y | A113 | BJ | 001-008, 115-199 | |
| 0259 | 22 | | GA | | 3-0 | 34-46-12 | D00433B | C07 | | | | TB0205Y | A042 | BJ | 009 | |
| 0259 | 22 | | GA | | 2-2 | 34-46-12 | D00433B | C07 | | | | TB0205Y | A042 | BJ | 010-099 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 110

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0260 | 20 | | GA | | 4-0 | SPARE | GD02112 | ST.. | 2 | | D41433J | | | AH | 115-199 |
| 0262 | 20 | | GA | | 1-6 | 22-41-12 | D41097J | | | EP | GD02106 | ST.. | 2 | | ALL |
| 0263 | 20 | | GA | | 1-6 | 22-41-12 | D41097J | | | EQ | GD02106 | ST.. | 2 | | 001-099 |
| 0263 | 20 | | GA | | 3-0 | 22-41-12 | GD02106 | ST.. | 2 | | D41097J | | | EQ | 115-199 |
| 0264 | 22 | | GA | | 4-9 | 22-32-14 | D00383A | J10 | | | SM00011 | | WI | | 001-010 |
| 0264 | 22 | | GA | | 5-1 | 22-32-14 | D00383A | J10 | | | TB0205Z | 13 | BJ | | 011-099 |
| 0264 | 22 | | GA | | 4-0 | 22-32-14 | D00383A | J10 | | | SM00011 | | WI | | 115-199 |
| 0265 | 22 | | GA | | 2-11 | 27-23-11 | D41695J | | 27 | | D41433J | | 38 | | 001-099 |
| 0265 | 22 | | GA | | 3-0 | 27-23-11 | D41433J | | 38 | | D41695J | | 27 | | 115-199 |
| 0266 | 22 | | GA | | 2-11 | 27-23-11 | D41695J | | 26 | | D41433J | | 37 | | 001-099 |
| 0266 | 22 | | GA | | 3-0 | 27-23-11 | D41433J | | 37 | | D41695J | | 26 | | 115-199 |
| 0274 | 20 | | GA | | 1-11 | 34-21-31 | D41890J | | 5 | | D41815J | | 11 | | 001-099 |
| 0274 | 20 | | GA | | 2-0 | 34-21-31 | D41890J | | 5 | | D41815J | | 11 | | 115-199 |
| 0277 | 24 | | GK | | 4-0 | 31-51-34 | D00085E | B11 | | | D41433J | | 39 | | 009 |
| 0277 | 24 | | GK | | 3-0 | 31-51-34 | D00085E | B11 | | | D41815J | | 37 | | 115-199 |
| 0278 | 24 | | GK | | 4-0 | 34-25-11 | D00919C | | 2 | | D40674J | | 3 | | 001, 003-099 |
| 0278 | 24 | | GK | | 5-0 | 34-25-11 | D00919C | | 2 | | D40674J | | 3 | | 115-199 |
| 0279 | 22 | | GA | | 2-4 | 34-25-11 | D00919C | | 4 | | GD02103 | AC.. | 2 | | 001, 003-099 |
| 0279 | 22 | | GA | | 2-0 | 34-25-11 | D00919C | | 4 | | GD02103 | AC.. | 2 | | 115-199 |
| 0280 | 24 | | GK | | 3-3 | 34-25-11 | D00919A | A01 | | | D41097J | | 52 | | 001, 003-099 |
| 0280 | 24 | | GK | | 3-0 | 34-25-11 | D00919A | A01 | | | D41097J | | 52 | | 115-199 |
| 0282 | 24 | | GK | | 4-5 | 34-25-11 | D00919A | A14 | | | D42083J | | 5 | | 001, 003-099 |
| 0282 | 24 | | GK | | 4-0 | 34-25-11 | D00919A | A14 | | | D42083J | | 5 | | 115-199 |
| 0283 | 20 | | GA | | 2-7 | 34-25-11 | GD02107 | ST.. | 2 | | D41097J | | | GY | 001, 003-099 |
| 0283 | 20 | | GA | | 1-6 | 34-25-11 | D41097J | | | DJ | GD02107 | ST.. | 2 | | 115-199 |
| 0284 | 20 | | GA | | 2-0 | 34-25-11 | GD02103 | ST.. | 2 | | D41349J | | | GW | 001, 003-099 |
| 0284 | 20 | | GA | | 1-6 | 34-25-11 | D41349J | | | DR | GD02103 | ST.. | 2 | | 115-199 |
| 0285 | 20 | | GA | | 2-7 | 34-25-11 | GD02107 | ST.. | 2 | | D41097J | | | GV | 001, 003-099 |
| 0285 | 20 | | GA | | 1-6 | 34-25-11 | D41097J | | | FP | GD02107 | ST.. | 2 | | 115-199 |
| 0286 | 20 | | GA | | 1-6 | 34-25-11 | D41349J | | | FQ | GD02103 | ST.. | 2 | | 115-199 |
| 0287 | 24 | | GK | | 3-9 | 34-22-16 | D00085D | B12 | | | D41605J | | 50 | | 001-099 |
| 0287 | 24 | | GK | | 3-0 | 34-22-16 | D41605J | | 50 | | D00085D | B12 | | | 115-199 |
| 0288 | 22 | | GA | | 3-7 | 22-32-13 | D00383B | E08 | | | GD02109 | DC.. | 2 | | 001-099 |
| 0288 | 22 | | GA | | 4-0 | 22-32-13 | D00383B | E08 | | | GD02109 | DC.. | 2 | | 115-199 |
| 0292 | 20 | | GA | | 2-1 | 31-31-42 | D41815J | | | LI | GD02107 | ST.. | 2 | | 001, 003-099 |
| 0292 | 20 | | GA | | 1-6 | 31-31-22 | D41815J | | | FD | GD02108 | ST.. | 2 | | 115-199 |
| 0293 | 24 | | GK | | 3-0 | 34-46-12 | D41433J | | 51 | | D00433B | D07 | | | 115-199 |
| 0294 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | A08 | | | TB0205X | B047 | BJ | | 009 |
| 0294 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | A08 | | | TB0205X | B047 | BJ | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 111

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | | | | | | | | | | | | | | | |
| | | 286N1175 | | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | |
| 0294 | 24 | GK | | | 2-0 | 34-46-12 | D00433B | A08 | | | GD02106 | DC.. | 2 | | 115-199 |
| 0295 | 22 | PA | | | 0-12 | 22-11-32 | D00055B | D03 | | | D00055B | K04 | | | 115-199 |
| 0296 | 22 | GA | | | 0-7 | 22-11-32 | D00055B | K13 | | | D00055B | K14 | | | 001-008 |
| 0297 | 22 | GA | | | 3-0 | 22-15-12 | D00055A | E03 | | | D41097J | 35 | | | ALL |
| 0298 | 22 | GA | | | 3-5 | 22-15-12 | D00055A | F09 | | | SM00029 | | WI | | 001-099 |
| 0298 | 22 | GA | | | 3-0 | 22-15-12 | D00055A | F09 | | | SM00029 | | WI | | 115-199 |
| 0299 | 22 | GA | | | 3-2 | 22-15-12 | D41815J | 31 | | | SM00029 | | WI | | 001-099 |
| 0299 | 22 | GA | | | 3-0 | 22-15-12 | D41815J | 31 | | | SM00029 | | WI | | 115-199 |
| 0300 | 22 | GA | | | 3-2 | 22-15-12 | D41815J | 32 | | | SM00029 | | WI | | 001-099 |
| 0300 | 22 | GA | | | 3-0 | 22-15-12 | D41815J | 32 | | | SM00029 | | WI | | 115-199 |
| 0302 | 24 | GK | | | 4-9 | 22-32-13 | D00383A | C09 | | | SM00011 | | WI | | 001-099 |
| 0302 | 24 | GK | | | 4-0 | 22-32-13 | D00383A | C09 | | | SM00011 | | WI | | 115-199 |
| 0304 | 22 | GA | | | 2-7 | 34-22-36 | D00085B | E09 | | | GD02112 | ST.. | # | | 001-099 |
| 0304 | 22 | GA | | | 3-0 | 34-22-36 | D00085B | E09 | | | GD02112 | ST.. | 2 | | 115-199 |
| 0306 | 24 | GK | | | 4-8 | 22-32-13 | D00383B | F13 | | | SM00011 | | WI | | 001-099 |
| 0306 | 24 | GK | | | 4-0 | 22-32-13 | D00383B | F13 | | | SM00011 | | WI | | 115-199 |
| 0308 | 20 | GA | | | 1-6 | 22-12-31 | D41815J | | | FK | GD02107 | ST.. | 2 | | 001-099 |
| 0308 | 20 | GA | | | 3-0 | 22-12-31 | D41815J | | | FK | GD02107 | ST.. | 2 | | 115-199 |
| 0310 | 22 | GA | | | 4-0 | 34-46-13 | D00433B | D06 | | | TB0205X | D052 | BJ | | 009 |
| 0310 | 22 | GA | | | 2-7 | 34-46-13 | D00433B | D06 | | | TB0205X | D052 | BJ | | 010-099 |
| 0311 | 20 | GA | | | 3-2 | 29-35-11 | D41622J | 13 | | | D41097J | 50 | | | 001-099 |
| 0311 | 20 | GA | | | 4-0 | 29-35-11 | D41097J | 50 | | | D41622J | 13 | | | 115-199 |
| 0312 | 20 | GA | | | 3-2 | 29-35-11 | D41622J | 14 | | | D41097J | 51 | | | 001-099 |
| 0312 | 20 | GA | | | 4-0 | 29-35-11 | D41097J | 51 | | | D41622J | 14 | | | 115-199 |
| 0313 | 24 | GK | | | 2-7 | 26-17-11 | D42167J | 1 | | | D41433J | 21 | | | 001-099 |
| 0313 | 24 | GK | | | 3-0 | 26-17-11 | D42167J | 1 | | | D41433J | 21 | | | 115-199 |
| 0314 | 24 | GK | | | 2-11 | 31-51-41 | D41695J | 25 | | | D41433J | 43 | | | 001-099 |
| 0314 | 24 | GK | | | 3-0 | 31-51-41 | D41695J | 25 | | | D41433J | 43 | | | 115-199 |
| 0315 | 24 | GK | | | 3-9 | 34-24-11 | D00447A | D02 | | | D42049J | 36 | | | 001-099 |
| 0315 | 24 | GK | | | 4-0 | 34-24-11 | D42049J | 36 | | | D00447A | D02 | | | 115-199 |
| 0316 | 24 | GK | | | 3-9 | 34-24-11 | D00447A | A02 | | | D42049J | 37 | | | 001-099 |
| 0316 | 24 | GK | | | 4-0 | 34-24-11 | D42049J | 37 | | | D00447A | A02 | | | 115-199 |
| 0317 | 24 | GK | | | 3-9 | 34-24-11 | D00447A | C02 | | | D42049J | 38 | | | 001-099 |
| 0317 | 24 | GK | | | 4-0 | 34-24-11 | D42049J | 38 | | | D00447A | C02 | | | 115-199 |
| 0318 | 24 | GK | | | 3-9 | 34-24-11 | D00447A | B02 | | | D42049J | 39 | | | 001-099 |
| 0318 | 24 | GK | | | 4-0 | 34-24-11 | D42049J | 39 | | | D00447A | B02 | | | 115-199 |
| 0319 | 22 | GA | | | 5-0 | 22-32-14 | D00383B | F04 | | | GD02103 | DC.. | # | | 115-199 |
| 0320 | 22 | GA | | | 3-0 | 34-22-16 | D41605J | 54 | | | TB0205Y | C077 | BJ | | 002 |
| 0323 | 22 | GA | | | 3-3 | 34-22-36 | D42049J | 40 | | | SM00001 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 112

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0323 | 22 | | GA | | 3-0 | 34-22-36 | | D42049J | 40 | | | SM00001 | | WI | | 115-199 |
| 0324 | 22 | | GA | | 2-0 | 22-11-32 | | D00055B | CAP | Y | | D00055B | CAP | Y | | 115-199 |
| 0325 | 22 | | GA | | 3-3 | 22-13-31 | | D00055B | H02 | | | SM00001 | | WI | | 001-099 |
| 0325 | 22 | | GA | | 3-0 | 22-13-31 | | D00055B | H02 | | | SM00001 | | WI | | 115-199 |
| 0326 | 22 | | GA | | 3-6 | 22-14-21 | | D42167J | 9 | | | D41815J | 39 | | | 001-099 |
| 0326 | 22 | | GA | | 4-0 | 22-14-21 | | D42167J | 9 | | | D41815J | 39 | | | 115-199 |
| 0327 | 24 | | GK | | 3-2 | 22-32-15 | | D00383A | D01 | | | TB0205Y | C087 | BJ | | 001-099 |
| 0327 | 24 | | GK | | 3-0 | 22-32-15 | | D00383A | D01 | | | TB0205Y | C087 | BJ | | 115-199 |
| 0331 | 22 | | GA | | 2-0 | 34-46-11 | | D00433B | D03 | | | SM00031 | | WI | | 115-199 |
| 0332 | 22 | | GA | | 2-0 | 34-46-11 | | D41433J | 32 | | | SM00006 | | WI | | 115-199 |
| 0333 | 22 | | GA | | 2-0 | 34-46-11 | | D41433J | 33 | | | SM00031 | | WI | | 115-199 |
| 0334 | 22 | | GA | | 2-1 | 22-14-11 | | D41815J | 38 | | | D42049J | 34 | | | 001-099 |
| 0334 | 22 | | GA | | 3-0 | 22-14-11 | | D42049J | 34 | | | D41815J | 38 | | | 115-199 |
| 0336 | 24 | | GK | | 4-8 | 22-32-13 | | D00383B | H07 | | | SM00011 | | WI | | 001-099 |
| 0336 | 24 | | GK | | 4-0 | 22-32-13 | | D00383B | H07 | | | SM00011 | | WI | | 115-199 |
| 0337 | 22 | | GA | | 2-2 | 22-14-11 | | D42049J | 14 | | | D41395J | 10 | | | 001-099 |
| 0337 | 22 | | GA | | 3-0 | 22-14-11 | | D41395J | 10 | | | D42049J | 14 | | | 115-199 |
| 0338 | 22 | | GA | | 3-3 | 77-11-11 | | D40674J | 1 | | | D41782J | 7 | | | 001-099 |
| 0338 | 22 | | GA | | 4-0 | 77-11-11 | | D40674J | 1 | | | D41782J | 7 | | | 115-199 |
| 0340 | 22 | | GA | | 2-6 | 34-22-36 | | D00085B | D11 | | | GD02111 | ST.. | 2 | | 001-008 |
| 0340 | 22 | | GA | | 3-0 | 34-22-36 | | D00085B | D11 | | | GD02111 | ST.. | 2 | | 009-099, 115-199 |
| 0341 | 22 | | GA | | 2-7 | 34-22-36 | | D00085B | E08 | | | GD02112 | ST.. | 2 | | 001-099 |
| 0341 | 22 | | GA | | 3-0 | 34-22-36 | | D00085B | E08 | | | GD02112 | ST.. | 2 | | 115-199 |
| 0343 | 22 | | GA | | 2-0 | 22-11-32 | | D00055B | C08 | | | D00055B | E08 | | | 115-199 |
| 0346 | 20 | | GA | | 1-6 | 22-32-11 | | D41349J | | | AT | GD02105 | ST.. | 2 | | 001-099 |
| 0346 | 20 | | GA | | 3-0 | 22-32-11 | | D41349J | | | AT | GD02105 | ST.. | 2 | | 115-199 |
| 0348 | 22 | | GA | | 2-0 | 34-25-11 | | D00919A | C10 | | | GD02103 | ST.. | 2 | | 115-199 |
| 0349 | 22 | | GA | | 2-0 | 34-25-11 | | D00919A | B13 | | | GD02103 | ST.. | 2 | | 115-199 |
| 0350 | 22 | | GA | | 2-0 | 34-25-11 | | D00919A | A10 | | | GD02103 | ST.. | 2 | | 115-199 |
| 0351 | 22 | | GA | | 2-7 | 34-22-36 | | D00085B | D10 | | | GD02112 | ST.. | # | | 001-099 |
| 0351 | 22 | | GA | | 3-0 | 34-22-36 | | D00085B | D10 | | | GD02112 | ST.. | # | | 115-199 |
| 0352 | 22 | | GA | | 2-6 | 34-22-36 | | D00085B | D07 | | | GD02111 | ST.. | # | | 001-008 |
| 0352 | 22 | | GA | | 3-0 | 34-22-36 | | D00085B | D07 | | | GD02111 | ST.. | # | | 009-099, 115-199 |
| 0353 | 22 | | GA | | 2-6 | 34-22-36 | | D00085B | G09 | | | GD02111 | ST.. | 2 | | 001-008 |
| 0353 | 22 | | GA | | 3-0 | 34-22-36 | | D00085B | G09 | | | GD02111 | ST.. | 2 | | 009-099 |
| 0353 | 22 | | GA | | 3-0 | 34-22-36 | | D00085B | G09 | | | GD02111 | ST.. | # | | 115-199 |
| 0354 | 22 | | GA | | 4-1 | 34-22-36 | | D00085B | D08 | | | SM00001 | | WI | | 001-099 |
| 0354 | 22 | | GA | | 3-0 | 34-22-36 | | D00085B | D08 | | | SM00001 | | WI | | 115-199 |
| 0355 | 22 | | GA | | 2-6 | 34-22-36 | | D00085B | D09 | | | GD02111 | ST.. | # | | 001-008 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 113

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|--|------------------------|------------------------|------------------|
| Wire No. | GA CO TY | Fam FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W1175 | 286N1175 | E2-3 INTEGRATION BUNDLE (continued) | | | |
| 0355 | 22 GA | 3-0 34-22-36 | D00085B D09 | GD02111 ST.. # | 009-099, 115-199 |
| 0356 | 22 GA | 2-6 34-22-36 | D00085B E11 | GD02111 ST.. # | 001-006 |
| 0356 | 22 GA | 2-6 34-22-36 | D00085B E11 | GD02111 ST.. 2 | 007-008 |
| 0356 | 22 GA | 3-0 34-22-36 | D00085B E11 | GD02111 ST.. # | 009-099, 115-199 |
| 0358 | 22 GA | 2-6 34-22-36 | D00085B F11 | GD02111 ST.. 2 | 001 |
| 0358 | 22 GA | 2-6 34-22-36 | D00085B F11 | GD02111 ST.. # | 002-008 |
| 0358 | 22 GA | 3-0 34-22-36 | D00085B F11 | GD02111 ST.. 2 | 009 |
| 0358 | 22 GA | 3-0 34-22-36 | D00085B F11 | GD02111 ST.. # | 010-099, 115-199 |
| 0359 | 20 GA | 1-6 22-33-11 | D41349J GO | GD02105 ST.. 2 | 001-099 |
| 0359 | 22 GA | 3-0 22-33-11 | D41349J GO | GD02105 ST.. 2 | 115-199 |
| 0360 | 20 GA | 1-6 22-33-11 | D41643J GP | GD02102 ST.. 2 | 001-099 |
| 0360 | 22 GA | 2-0 22-33-11 | D41643J GP | GD02102 ST.. 2 | 115-199 |
| 0361 | 22 GA | 2-0 34-25-11 | D00919A C06 | GD02102 DC.. 2 | 115-199 |
| 0362 | 20 GA | 1-6 34-22-38 | D41349J CQ | GD02105 ST.. 2 | 001-099 |
| 0362 | 20 GA | 3-0 34-22-38 | D41349J CQ | GD02105 ST.. 2 | 115-199 |
| 0363 | 20 GA | 1-6 22-33-11 | D41643J IC | GD02102 ST.. 2 | 001-099 |
| 0363 | 22 GK | 1-6 22-33-11 | D41643J IC | GD02102 ST.. 2 | 115-199 |
| 0364 | 20 GA | 1-6 22-33-11 | D41349J ID | GD02105 ST.. 2 | 001-099 |
| 0364 | 22 GK | 1-6 22-33-11 | D41349J ID | GD02105 ST.. 2 | 115-199 |
| 0365 | 24 GK | 5-0 SPARE | D41643J 17 | D42021J 6 | 115-199 |
| 0366 | 24 GK | 5-0 SPARE | D41643J 18 | D42021J 7 | 115-199 |
| 0369 | 24 GK | 3-2 34-45-01 | D41815J 13 | D00085E E11 | 001-099 |
| 0369 | 24 GK | 3-0 34-45-01 | D41815J 13 | D00085A REF VM | 115-199 |
| 0370 | 22 GA | 2-3 22-14-11 | D41349J 40 | SM00018 WI | 001-099 |
| 0371 | 22 GA | 2-10 22-14-21 | D42167J 2 | SM00013 WI | 001-099 |
| 0372 | 20 GA | 4-4 22-31-12 | D41884J 10 | D00383C 5 | 001-099 |
| 0373 | 22 GA | 2-9 22-11-12 | D41643J 22 | SM00014 WI | 001-099 |
| 0374 | 22 GA | 2-9 22-11-12 | D41643J 23 | SM00015 WI | 001-099 |
| 0375 | 22 GA | 2-5 22-11-22 | D41433J 28 | SM00013 WI | 001-099 |
| 0377 | 22 GA | 2-3 22-11-22 | D41349J 38 | SM00014 WI | 001-099 |
| 0378 | 22 GA | 2-3 22-11-22 | D41349J 39 | SM00015 WI | 001-099 |
| 0379 | 22 GA | 2-3 22-11-32 | D41884J 11 | SM00013 WI | 001-099 |
| 0380 | 22 GA | 3-2 22-11-32 | D00055C 9 | SM00013 WI | 001-099 |
| 0381 | 22 GA | 2-3 22-14-11 | D41349J 44 | SM00018 WI | 001-099 |
| 0382 | 22 GA | 2-11 22-14-21 | D41605J 40 | SM00018 WI | 001-099 |
| 0383 | 22 GA | 2-11 22-14-21 | D41605J 48 | SM00003 WI | 001-099 |
| 0384 | 22 GA | 3-2 22-14-31 | D00055A F01 | D41349J 42 | 001-099 |
| 0385 | 22 GA | 3-0 22-11-32 | D00055B C13 | D00055B F04 | 001 |
| 0386 | 22 GA | 3-6 22-14-31 | D00055B K03 | D41643J 3 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 114

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0387 | 22 | | GA | | 2-5 | 22-14-31 | D00055B | | G12 | | D41395J | 33 | | | 001-099 |
| 0388 | 22 | | GA | | 3-8 | 22-14-31 | D00055A | | F03 | | D41643J | 20 | | | 001-099 |
| 0389 | 22 | | GA | | 3-6 | 22-14-31 | D00055B | | E12 | | D41643J | 21 | | | 001-099 |
| 0390 | 22 | | GA | | 3-3 | 22-14-31 | D00055B | | K02 | | SM00018 | | WI | | 001-099 |
| 0391 | 22 | | GA | | 4-0 | 22-15-12 | D00055A | | K03 | | D41567J | 47 | | | 001-099 |
| 0392 | 22 | | GA | | 3-0 | 22-15-12 | D00055A | | K01 | | D41605J | 41 | | | 001-099 |
| 0393 | 22 | | GA | | 3-8 | 22-41-13 | D00055B | | F09 | | D42167J | 3 | | | 001-099 |
| 0394 | 22 | | GA | | 3-1 | 22-41-13 | D00055B | | F10 | | D42021J | 15 | | | 001-099 |
| 0395 | 22 | | GA | | 3-0 | 22-41-11 | D00055A | | A03 | | D41097J | 21 | | | 001-099 |
| 0396 | 22 | | GA | | 4-3 | 22-41-11 | D00383B | | C15 | | D41097J | 22 | | | 001-099 |
| 0397 | 22 | | GA | | 3-2 | 22-15-12 | D00055A | | G01 | | D41349J | 31 | | | 001-099 |
| 0398 | 22 | | GA | | 3-0 | 22-41-11 | D00055B | | C06 | | D41349J | 32 | | | 001-099 |
| 0399 | 22 | | GA | | 2-5 | 22-11-12 | D41433J | | 27 | | SM00013 | | WI | | 001-099 |
| 0400 | 22 | | GA | | 3-3 | 22-11-32 | D00055B | | A06 | | SM00014 | | WI | | 001-099 |
| 0401 | 22 | | GA | | 3-9 | 22-11-32 | D41888J | | 1 | | SM00014 | | WI | | 001-099 |
| 0402 | 22 | | GA | | 3-9 | 22-11-32 | D41888J | | 2 | | SM00015 | | WI | | 001-099 |
| 0403 | 22 | | GA | | 3-3 | 22-11-32 | D00055B | | C07 | | SM00015 | | WI | | 001-099 |
| 0405 | 22 | | GA | | 5-0 | 22-32-14 | D00383A | | D11 | | GD02104 | DC.. | 2 | | 115-199 |
| 0406 | 22 | | GA | | 2-3 | 34-46-12 | D00433B | | D14 | | GD02106 | ST.. | 2 | | 001, 003-008 |
| 0406 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | D14 | | TB0205Z | 59 | BJ | | 009-099 |
| 0406 | 22 | | GA | | 2-0 | 34-46-12 | D00433B | | D14 | | GD02106 | ST.. | 2 | | 115-199 |
| 0407 | 20 | | GA | | 1-6 | 34-46-12 | D41433J | | | IE | GD02103 | ST.. | 2 | | ALL |
| 0408 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | C15 | | TB0205X | C054 | BJ | | 009 |
| 0408 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | | C15 | | TB0205X | C054 | BJ | | 010-099 |
| 0408 | 22 | | GA | | 2-0 | 34-46-12 | D00433B | | C15 | | GD02106 | ST.. | 2 | | 115-199 |
| 0409 | 24 | | GK | | 4-3 | 73-21-22 | D41784J | | 2 | | D41349J | 43 | | | 001-099 |
| 0410 | 24 | | GK | | 4-3 | 73-21-22 | D41784J | | 1 | | D41349J | 45 | | | 001-099 |
| 0411 | 24 | | GK | | 2-9 | 34-45-02 | D41643J | | 25 | | SM00031 | | WI | | 001, 003-099 |
| 0411 | 24 | | GK | | 2-0 | 34-45-02 | D41643J | | 25 | | SM00031 | | WI | | 115-199 |
| 0412 | 22 | | GA | | 2-9 | 34-45-02 | D41643J | | 26 | | SM00006 | | WI | | 001, 003-099 |
| 0412 | 22 | | GA | | 2-0 | 34-45-02 | D41643J | | 26 | | SM00006 | | WI | | 115-199 |
| 0413 | 22 | | GA | | 4-7 | 34-45-02 | D41643J | | 27 | | TB0205Z | 115 | BJ | | 001, 003-099 |
| 0413 | 22 | | GA | | 5-0 | 34-45-02 | D41643J | | 27 | | TB0205Z | 115 | BJ | | 115-199 |
| 0414 | 22 | | GA | | 2-9 | 22-13-11 | D41643J | | 32 | | SM00030 | | WI | | 001-099 |
| 0414 | 22 | | GA | | 2-0 | 22-13-11 | D41643J | | 32 | | SM00030 | | WI | | 115-199 |
| 0415 | 22 | | GA | | 2-1 | 22-13-11 | D41643J | | | JF | GD02102 | ST.. | 2 | | 001-010 |
| 0415 | 22 | | GA | | 2-1 | 22-13-11 | D41643J | | | JF | GD02102 | ST.. | 2 | *1 | 011-099 |
| 0415 | 22 | | GA | | 2-0 | 22-13-11 | D41643J | | | JF | GD02102 | ST.. | 2 | | 115-199 |
| 0416 | 22 | | GA | | 3-8 | 34-31-11 | D40674J | | 8 | | D00203C | 2 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 115

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0416 | 22 | | GA | | 4-0 | 34-31-11 | D40674J | | 8 | | D02939C | | 9 | | 115-199 |
| 0417 | 22 | | GA | | 2-4 | 34-31-11 | D00203C | | 3 | | GD02103 | AC.. | 2 | | 001-099 |
| 0417 | 22 | | GA | | 2-0 | 34-31-11 | D02939C | | 7 | | GD02103 | AC.. | 2 | | 115-199 |
| 0418 | 22 | | GA | | 2-4 | 34-31-11 | D00203C | | 4 | | GD02103 | ST.. | 2 | *2 | 001-099 |
| 0418 | 22 | | GA | | 2-0 | 34-31-11 | D02939C | | 8 | | GD02103 | ST.. | 2 | *2 | 115-199 |
| 0419 | 24 | | GK | | 0-7 | 34-31-11 | D00203B | | B03 | | D00203B | C03 | | | 001-099 |
| 0420 | 24 | | GK | | 0-7 | 34-31-11 | D00203B | | B05 | | D00203B | C05 | | | 001-099 |
| 0421 | 22 | | GA | | 2-9 | 34-31-11 | D00203B | | D15 | | D41643J | | 39 | | 001-099 |
| 0421 | 22 | | GA | | 3-0 | 34-31-11 | D02939B | | A04 | | D41643J | | 39 | | 115-199 |
| 0422 | 22 | | GA | | 2-3 | 34-45-01 | D41815J | | | JA | GD02110 | ST.. | 2 | | 001-099 |
| 0422 | 22 | | GA | | 3-0 | 34-45-01 | D41815J | | | JA | GD02110 | ST.. | 2 | | 115-199 |
| 0423 | 22 | | GA | | 2-10 | 34-46-11 | SM00031 | | | | D00433B | D03 | | | 001, 003-099 |
| 0423 | 22 | | GA | | 5-0 | 34-46-11 | D00433B | | D03 | WI | TB0205Y | C099 | 2 | | 002 |
| 0425 | 22 | | GA | | 2-1 | 34-31-11 | GD02102 | | ST.. | 2 | D41643J | | | JE | 001-010 |
| 0425 | 22 | | GA | | 2-1 | 34-31-11 | GD02102 | | ST.. | 2 | D41643J | | | JE | 011-099 |
| 0425 | 22 | | GA | | 2-0 | 34-31-11 | GD02102 | | ST.. | 2 | D41643J | | | JE | 115-199 |
| 0426 | 20 | | GA | | 2-9 | 34-31-11 | D42105J | | 5 | | SM00030 | | WI | | 001-099 |
| 0426 | 20 | | GA | | 4-0 | 34-31-11 | D42105J | | 5 | | SM00030 | | WI | | 115-199 |
| 0427 | 22 | | GA | | 3-0 | 34-31-11 | D42105J | | 11 | | D41643J | | 41 | | 001-099 |
| 0427 | 22 | | GA | | 5-0 | 34-31-11 | D42105J | | 11 | | D41643J | | 41 | | 115-199 |
| 0428 | 22 | | GA | | 2-6 | 22-13-11 | D00203B | | C01 | | SM00030 | | WI | | 001-099 |
| 0428 | 22 | | GA | | 2-0 | 22-13-11 | D02939B | | F15 | | SM00030 | | WI | | 115-199 |
| 0433 | 22 | | GA | | 4-0 | 34-25-12 | D42167J | | 5 | | D00085D | | F13 | | 002 |
| 0446 | 22 | | GA | | 4-0 | 34-46-13 | D00433A | | B11 | | TB0205X | B045 | BJ | | 009 |
| 0446 | 22 | | GA | | 2-9 | 34-46-13 | D00433A | | B11 | | TB0205X | B045 | BJ | | 010-099 |
| 0447 | 22 | | GA | | 4-0 | 34-46-13 | D00433A | | C11 | | TB0205X | C045 | BJ | | 009 |
| 0447 | 22 | | GA | | 2-9 | 34-46-13 | D00433A | | C11 | | TB0205X | C045 | BJ | | 010-099 |
| 0448 | 22 | | GA | | 4-0 | 34-46-13 | D00433A | | B05 | | TB0205X | A046 | BJ | | 009 |
| 0448 | 22 | | GA | | 2-9 | 34-46-13 | D00433A | | B05 | | TB0205X | A046 | BJ | | 010-099 |
| 0449 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | B02 | | TB0205X | B048 | BJ | | 009 |
| 0449 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | | B02 | | TB0205X | B048 | BJ | | 010-099 |
| 0450 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | A07 | | TB0205X | A053 | BJ | | 009 |
| 0450 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | | A07 | | TB0205X | A053 | BJ | | 010-099 |
| 0451 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | D05 | | TB0205X | D051 | BJ | | 009 |
| 0451 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | | D05 | | TB0205X | D051 | BJ | | 010-099 |
| 0452 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | A05 | | TB0205X | A051 | BJ | | 009 |
| 0452 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | | A05 | | TB0205X | A051 | BJ | | 010-099 |
| 0453 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | B05 | | TB0205X | B051 | BJ | | 009 |
| 0453 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | | B05 | | TB0205X | B051 | BJ | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 116

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1175 | 286N1175 | | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0454 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | B08 | | | | TB0205X | B053 | BJ | | 009-099 |
| 0455 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | A15 | | | | TB0205X | A054 | BJ | | 009 |
| 0455 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | A15 | | | | TB0205X | A054 | BJ | | 010-099 |
| 0456 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | B15 | | | | TB0205X | B054 | BJ | | 009-099 |
| 0457 | 22 | | GA | | 2-5 | 34-46-13 | TB0205Z | 57 | BJ | | | GD02106 | ST.. | 2 | | 009-099 |
| 0458 | 22 | | GA | | 1-9 | 34-46-13 | TB0205Z | 59 | BJ | | | GD02108 | ST.. | 2 | | 009-099 |
| 0482 | 22 | | GA | | 2-9 | 22-32-14 | TB0205Z | 13 | BJ | | | SM00011 | | WI | | 011-099 |
| 0483 | 22 | | GA | | 1-8 | 22-32-14 | TB0205X | A011 | BJ | | | GD02102 | DC.. | 2 | | 011-099 |
| 0484 | 22 | | GA | | 1-8 | 22-32-14 | TB0205X | B011 | BJ | | | GD02102 | DC.. | 2 | | 011-099 |
| 0485 | 22 | | GA | | 1-8 | 22-32-14 | TB0205X | C011 | BJ | | | GD02102 | DC.. | 2 | | 011-099 |
| 0486 | 22 | | GA | | 1-8 | 22-32-14 | TB0205X | D011 | BJ | | | GD02102 | DC.. | 2 | | 011-099 |
| 0487 | 22 | | GA | | 1-8 | 22-32-14 | TB0205X | A012 | BJ | | | GD02102 | DC.. | 2 | | 011-099 |
| 0488 | 22 | | GA | | 1-8 | 22-32-14 | TB0205X | B012 | BJ | | | GD02102 | DC.. | 2 | | 011-099 |
| 0491 | 22 | | GA | | 1-7 | 22-11-32 | D00055A | D04 | | | | D00055B | A04 | | | 001-008 |
| 0491 | 22 | | GA | | 1-0 | 22-11-32 | D00055A | D04 | | | | D00055B | A04 | | | 115-199 |
| 0501 | 24 | | GK | | 3-2 | 34-45-01 | D41815J | 12 | | | | D00085E | G11 | | | 003-099 |
| 0502 | 22 | | GA | | 2-3 | 34-45-01 | D41815J | | | | ET | GD02110 | ST.. | 2 | | 003-099 |
| 0512 | 22 | | GA | | 0-7 | 22-11-32 | D00055B | A12 | | | | D00055B | B15 | | | 001-008 |
| 0512 | 22 | | GA | | 2-0 | 22-11-32 | D00055B | A12 | | | | D00055B | B15 | | | 115-199 |
| 0516 | 22 | | GA | | 3-0 | 34-22-36 | D00085A | A14 | | | | GD02108 | ST.. | 2 | | 002 |
| 0523 | 22 | | GA | | 2-8 | 34-22-36 | D00085A | B10 | | | | GD02111 | ST.. | # | | 003-008 |
| 0523 | 22 | | GA | | 3-0 | 34-22-36 | D00085A | B10 | | | | GD02111 | ST.. | 2 | | 009-099 |
| 0524 | 22 | | GA | | 2-6 | 34-22-36 | D00085B | G03 | | | | GD02111 | ST.. | # | | 003-008 |
| 0524 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | G03 | | | | GD02111 | ST.. | 2 | | 009-099 |
| 0525 | 22 | | GA | | 2-6 | 34-22-36 | D00085B | H03 | | | | GD02111 | ST.. | # | | 003-008 |
| 0525 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | H03 | | | | GD02111 | ST.. | 2 | | 009-099 |
| 0526 | 22 | | GA | | 2-6 | 34-22-36 | D00085B | J04 | | | | GD02111 | ST.. | # | | 003-008 |
| 0526 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | J04 | | | | GD02111 | ST.. | 2 | | 009-099 |
| 0530 | 22 | | GA | | 3-0 | 34-43-14 | TB0205A | A010 | 2 | | | TB0205A | A009 | 2 | | 002 |
| 0531 | 22 | | GA | | 3-4 | 34-43-14 | D41823J | 11 | | | | TB0205Y | A095 | BJ | | 002 |
| 0536 | 20 | | GA | | 2-0 | 34-46-12 | D41349J | | | | MA | GD02105 | ST.. | 2 | | 002 |
| 0537 | 20 | | GA | | 1-6 | 34-46-12 | GD02109 | ST.. | 2 | | | D41395J | | | NN | 002 |
| 0541 | 22 | | GA | | 5-0 | 34-43-14 | D41823J | 12 | | | | TB0205Y | C077 | BJ | | 002 |
| 0544 | 20 | | GA | | 5-0 | 34-58-11 | GD02115 | ST.. | 2 | | | D41819J | | | AB | 115-199 |
| 0545 | 20 | | GA | | 5-0 | 34-58-11 | GD02105 | ST.. | 2 | | | D41349J | | | AI | 115-199 |
| 0546 | 20 | | GA | | 5-0 | 34-58-11 | GD02103 | ST.. | 2 | | | D41643J | | | AJ | 115-199 |
| 0547 | 20 | | GA | | 5-0 | 34-58-11 | D41815J | | | | AK | GD02108 | ST.. | 2 | | 115-199 |
| 0549 | 24 | | GK | | 1-0 | 34-31-11 | D02939B | K04 | | | | D02939B | B05 | | | 115-199 |
| 0551 | 22 | | GA | | 5-0 | 34-22-36 | D00085B | J02 | | | | GD02108 | ST.. | 2 | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 117

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0551 | 22 | | PA | | 5-0 | 34-22-36 | D00085B | J02 | | | GD02108 | ST.. | 2 | | 115-199 |
| 0554 | 24 | | GK | | 1-0 | 34-31-31 | D02943B | B05 | | | D02943B | K04 | | | 115-199 |
| 0557 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | B02 | | | GD02111 | ST.. | 2 | | 009-099 |
| 0560 | 22 | | GA | | 4-0 | 34-22-16 | D41605J | 39 | | | TB0205Y | C078 | BJ | | 002 |
| 0563 | 22 | | GA | | 3-0 | 22-11-32 | D00055B | F11 | | | D00055B | K09 | | | 001, 115-199 |
| 0566 | 22 | | GA | | 6-0 | 34-22-18 | D41643J | 10 | | | D00085E | H11 | | | 002 |
| 0568 | 22 | | GA | | 4-0 | 34-22-36 | D00085B | K05 | | | GD02108 | ST.. | 2 | | 002 |
| 0569 | 22 | | GA | | 2-7 | 34-22-36 | D00085B | H06 | | | GD02112 | ST.. | 2 | | 010-099 |
| 0571 | 22 | | GA | | 4-0 | 34-22-18 | D41643J | 24 | | | D23005J | 22 | | | 002 |
| 0572 | 22 | | GA | | 5-0 | 34-22-36 | D00085B | E06 | | | GD02108 | ST.. | 2 | | 002 |
| 0572 | 22 | | PA | | 4-0 | 34-22-36 | D00085B | E06 | | | GD02108 | ST.. | 2 | | 115-199 |
| 0575 | 22 | | GA | | 2-6 | 34-22-36 | D00085B | D05 | | | GD02111 | ST.. | 2 | | 001-008 |
| 0575 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | D05 | | | GD02111 | ST.. | # | | 009 |
| 0575 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | D05 | | | GD02111 | ST.. | 2 | | 010-099 |
| 0576 | 22 | | GA | | 2-6 | 34-22-36 | D00085B | F06 | | | GD02111 | ST.. | 2 | | 001-008 |
| 0576 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | F06 | | | GD02111 | ST.. | 2 | | 009-099 |
| 0577 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | K04 | | | GD02110 | ST.. | 2 | | 001-099 |
| 0578 | 22 | | GA | | 3-0 | 34-22-18 | D41643J | 40 | | | D23005J | 23 | | | 002 |
| 0579 | 22 | | GA | | 4-0 | 34-22-26 | D41605J | 55 | | | TB0205Y | C077 | BJ | | 002 |
| 0580 | 22 | | GA | | 4-0 | 34-22-26 | D41605J | 51 | | | TB0205Y | C078 | BJ | | 002 |
| 0581 | 22 | | GA | | 2-0 | 34-22-38 | D41819J | | | LA | GD02115 | ST.. | 2 | | 115-199 |
| 0582 | 22 | | GA | | 2-5 | 34-22-36 | D00085B | D12 | | | GD02113 | ST.. | # | | 001-099 |
| 0582 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | D12 | | | GD02111 | ST.. | 2 | | 115-199 |
| 0583 | 22 | | GA | | 3-0 | 34-22-38 | D41605J | | | LC | GD02106 | ST.. | 2 | | 115-199 |
| 0584 | 22 | | GA | | 3-0 | 34-22-36 | D00085B | E12 | | | GD02111 | ST.. | # | | 115-199 |
| 0585 | 22 | | GA | | 6-0 | 34-22-28 | D23003J | 22 | | | D42083J | 6 | | | 002 |
| 0586 | 22 | | GA | | 4-0 | 34-22-28 | D23003J | 23 | | | D41349J | 13 | | | 002 |
| 0587 | 22 | | GA | | 4-0 | 34-22-36 | D00085A | H14 | | | TB0205Y | C078 | BJ | | 002 |
| 0588 | 22 | | GA | | 4-0 | 34-22-36 | D00085A | K14 | | | TB0205Y | C077 | BJ | | 002 |
| 0589 | 20 | | GA | | 3-0 | 34-46-12 | D41349J | | | IS | GD02102 | ST.. | 2 | | 002 |
| 0594 | 20 | | GA | | 3-0 | 34-46-12 | D41349J | | | IT | GD02102 | ST.. | 2 | | 002 |
| 0596 | 22 | | GA | | 4-0 | 34-22-36 | D00085B | G06 | | | GD02108 | ST.. | 2 | | 002 |
| 0596 | 22 | | GA | | 2-7 | 34-22-36 | D00085B | G06 | | | GD02112 | ST.. | 2 | | 010-099 |
| 0596 | 22 | | PA | | 4-0 | 34-22-36 | D00085B | G06 | | | GD02108 | ST.. | 2 | | 115-199 |
| 0597 | 22 | | GA | | 4-0 | 34-46-14 | D23005J | 1 | | | D00433A | D10 | | | 002 |
| 0598 | 22 | | GA | | 4-0 | 34-46-14 | D23005J | 5 | | | D00433A | C07 | | | 002 |
| 0599 | 22 | | GA | | 4-0 | 34-46-14 | D23003J | 7 | | | D00433B | C14 | | | 002 |
| 0601 | 22 | | GA | | 3-11 | 34-46-11 | D00433B | A03 | | | TB0205Z | 117 | BJ | | 001, 003-008 |
| 0601 | 22 | | GA | | 4-0 | 34-46-11 | D00433B | A03 | | | TB0205Z | 117 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 118

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0602 | 22 | | GA | | 4-1 | 34-46-11 | D00433A | | D10 | | TB0205Z | 117 | BJ | | 001, 003-008 |
| 0602 | 22 | | GA | | 4-0 | 34-46-13 | D00433A | | D10 | | TB0205Z | 57 | BJ | | 009-099 |
| 0602 | 22 | | GA | | 4-0 | 34-46-11 | D00433A | | D10 | | TB0205Z | 117 | BJ | | 115-199 |
| 0603 | 22 | | GA | | 4-1 | 34-46-12 | D00433A | | B10 | | TB0205Z | 117 | BJ | | 001, 003-008 |
| 0603 | 22 | | GA | | 4-0 | 34-46-13 | D00433A | | B10 | | TB0205Z | 57 | BJ | | 009-099 |
| 0603 | 22 | | GA | | 4-0 | 34-46-12 | D00433A | | B10 | | TB0205Z | 117 | BJ | | 115-199 |
| 0604 | 22 | | GA | | 4-1 | 34-46-12 | D00433A | | C10 | | TB0205Z | 117 | BJ | | 001, 003-008 |
| 0604 | 22 | | GA | | 4-0 | 34-46-13 | D00433A | | C10 | | TB0205Z | 57 | BJ | | 009-099 |
| 0604 | 22 | | GA | | 4-0 | 34-46-12 | D00433A | | C10 | | TB0205Z | 117 | BJ | | 115-199 |
| 0605 | 22 | | GA | | 4-1 | 34-46-12 | D00433A | | A11 | | TB0205Z | 117 | BJ | | 001, 003-008 |
| 0605 | 22 | | GA | | 4-0 | 34-46-13 | D00433A | | A11 | | TB0205Z | 57 | BJ | | 009-099 |
| 0605 | 22 | | GA | | 4-0 | 34-46-12 | D00433A | | A11 | | TB0205Z | 117 | BJ | | 115-199 |
| 0606 | 22 | | GA | | 4-1 | 34-46-11 | D00433A | | A12 | | TB0205Z | 115 | BJ | | 001, 003-099 |
| 0606 | 22 | | GA | | 4-1 | 34-46-11 | D00433A | | A12 | | TB0205A | C010 | 2 | | 002 |
| 0606 | 22 | | GA | | 4-0 | 34-46-11 | D00433A | | A12 | | TB0205Z | 115 | BJ | | 115-199 |
| 0607 | 22 | | GA | | 3-2 | 34-46-11 | D42021J | | 4 | | TB0205Z | 115 | BJ | | 001-099 |
| 0607 | 22 | | GA | | 4-0 | 34-46-11 | D42021J | | 27 | | TB0205Z | 115 | BJ | | 115-199 |
| 0608 | 22 | | GA | | 3-11 | 34-22-26 | D41605J | | 53 | | TB0205Z | 115 | BJ | | 001, 003-099 |
| 0608 | 22 | | GA | | 3-11 | 34-22-26 | D41605J | | 53 | | TB0205Z | 91 | BJ | | 002 |
| 0608 | 22 | | GA | | 4-0 | 34-22-26 | D41605J | | 53 | | TB0205Z | 115 | BJ | | 115-199 |
| 0609 | 22 | | GA | | 3-11 | 34-22-16 | D41605J | | 52 | | TB0205Z | 115 | BJ | | 001, 003-099 |
| 0609 | 22 | | GA | | 3-11 | 34-22-16 | D41605J | | 52 | | TB0205Z | 91 | BJ | | 002 |
| 0609 | 22 | | GA | | 4-0 | 34-22-16 | D41605J | | 52 | | TB0205Z | 115 | BJ | | 115-199 |
| 0610 | 22 | | GA | | 2-9 | 34-22-36 | D00085A | | K13 | | TB0205Z | 115 | BJ | | 001, 003-099 |
| 0610 | 22 | | GA | | 2-9 | 34-22-36 | D00085A | | K13 | | TB0205Z | 91 | BJ | | 002 |
| 0610 | 22 | | GA | | 3-0 | 34-22-36 | D00085A | | K13 | | TB0205Z | 115 | BJ | | 115-199 |
| 0611 | 22 | | GA | | 2-9 | 34-22-36 | D00085A | | C14 | | TB0205Z | 115 | BJ | | 001, 003-099 |
| 0611 | 22 | | GA | | 2-9 | 34-22-36 | D00085A | | C14 | | TB0205Z | 91 | BJ | | 002 |
| 0611 | 22 | | GA | | 3-0 | 34-22-36 | D00085A | | C14 | | TB0205Z | 115 | BJ | | 115-199 |
| 0612 | 24 | | GK | | 3-11 | 31-51-21 | D41097J | | 48 | | TB0205Z | 115 | BJ | | 001-099 |
| 0612 | 24 | | GK | | 4-0 | 31-51-21 | D41097J | | 48 | | TB0205Z | 115 | BJ | | 115-199 |
| 0614 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | C02 | | TB0205X | C048 | BJ | | 009 |
| 0614 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | | C02 | | TB0205X | C048 | BJ | | 010-099 |
| 0615 | 22 | | GA | | 4-1 | 34-46-12 | D00433A | | D12 | | TB0205Y | A113 | BJ | | 001, 003-008 |
| 0615 | 22 | | GA | | 3-0 | 34-46-12 | D00433A | | D12 | | TB0205Y | A042 | BJ | | 009 |
| 0615 | 22 | | GA | | 2-3 | 34-46-12 | D00433A | | D12 | | TB0205Y | A042 | BJ | | 010-099 |
| 0615 | 22 | | GA | | 4-0 | 34-46-12 | D00433A | | D12 | | TB0205Y | A113 | BJ | | 115-199 |
| 0616 | 22 | | GA | | 4-3 | 34-46-12 | D41433J | | 17 | | TB0205Y | A113 | BJ | | 001-008 |
| 0616 | 22 | | GA | | 2-5 | 34-46-12 | D41433J | | 17 | | TB0205Y | A042 | BJ | | 009-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 119

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | | | | | | | | | | | | | | | |
| | | 286N1175 | | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | |
| 0616 | 22 | GA | | | 5-0 | 34-46-12 | D41433J | | 17 | | TB0205Y | A113 | BJ | | 115-199 |
| 0617 | 22 | GA | | | 2-8 | 34-22-36 | D00085D | | D12 | | GD02111 | ST.. | 2 | | 001-008 |
| 0617 | 22 | GA | | | 3-0 | 34-22-36 | D00085D | | D12 | | GD02111 | ST.. | 2 | | 009-099, 115-199 |
| 0618 | 22 | GA | | | 2-8 | 34-22-37 | D00085D | | J13 | | GD02111 | ST.. | 2 | | 001-008 |
| 0618 | 22 | GA | | | 3-0 | 34-22-37 | D00085D | | J13 | | GD02111 | ST.. | 2 | | 009-099, 115-199 |
| 0619 | 24 | GK | | | 3-1 | 34-22-37 | D00085A | | A11 | | D41567J | | 54 | | 001-099 |
| 0619 | 24 | GK | | | 3-0 | 34-22-37 | D00085A | | A11 | | D41567J | | 54 | | 115-199 |
| 0621 | 22 | GA | | | 3-11 | 34-46-11 | D00433B | | C08 | | TB0205Z | | 117 | BJ | 001, 003-008 |
| 0621 | 22 | GA | | | 4-0 | 34-46-13 | D00433B | | C08 | | TB0205Z | | 59 | BJ | 009-099 |
| 0621 | 22 | GA | | | 4-0 | 34-46-11 | D00433B | | C08 | | TB0205Z | | 117 | BJ | 115-199 |
| 0622 | 22 | GA | | | 0-7 | 22-11-32 | D00055B | | J02 | | D00055B | | J04 | | 001-008 |
| 0623 | 22 | GA | | | 0-7 | 22-11-32 | D00055B | | B12 | | D00055B | | D15 | | 001-008 |
| 0623 | 22 | GA | | | 2-0 | 22-11-32 | D00055B | | B12 | | D00055B | | D15 | | 115-199 |
| 0624 | 22 | GA | | | 4-0 | 34-46-14 | D23003J | | 8 | | D00433A | | D07 | | 002 |
| 0625 | 22 | GA | | | 4-0 | 34-46-13 | D00433B | | C06 | | TB0205X | | C052 | BJ | 009 |
| 0625 | 22 | GA | | | 2-7 | 34-46-13 | D00433B | | C06 | | TB0205X | | C052 | BJ | 010-099 |
| 0626 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | C13 | | TB0205X | | A030 | BJ | 009 |
| 0626 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | C13 | | TB0205X | | A029 | BJ | 010-099 |
| 0627 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | A12 | | TB0205X | | B030 | BJ | 009 |
| 0627 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | A12 | | TB0205X | | B030 | BJ | 010-099 |
| 0628 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | B12 | | TB0205X | | C030 | BJ | 009 |
| 0628 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | B12 | | TB0205X | | C030 | BJ | 010-099 |
| 0629 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | C12 | | TB0205X | | D029 | BJ | 009 |
| 0629 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | C12 | | TB0205X | | D029 | BJ | 010-099 |
| 0630 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | A13 | | TB0205X | | A031 | BJ | 009 |
| 0630 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | A13 | | TB0205X | | A031 | BJ | 010-099 |
| 0631 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | B13 | | TB0205X | | B031 | BJ | 009 |
| 0631 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | B13 | | TB0205X | | B031 | BJ | 010-099 |
| 0632 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | C11 | | TB0205X | | C031 | BJ | 009 |
| 0632 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | C11 | | TB0205X | | C031 | BJ | 010-099 |
| 0633 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | F11 | | TB0205X | | D032 | BJ | 009 |
| 0633 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | F11 | | TB0205X | | D032 | BJ | 010-099 |
| 0634 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | D12 | | TB0205X | | A033 | BJ | 009 |
| 0634 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | D12 | | TB0205X | | A033 | BJ | 010-099 |
| 0635 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | F12 | | TB0205X | | B033 | BJ | 009 |
| 0635 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | F12 | | TB0205X | | B033 | BJ | 010-099 |
| 0636 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | H12 | | TB0205X | | C033 | BJ | 009 |
| 0636 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | H12 | | TB0205X | | C033 | BJ | 010-099 |
| 0637 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | G13 | | TB0205X | | D033 | BJ | 009 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 120

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0637 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | G13 | | TB0205X | D033 | BJ | | 010-099 |
| 0638 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | C10 | | TB0205X | A035 | BJ | | 009 |
| 0638 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | C10 | | TB0205X | A035 | BJ | | 010-099 |
| 0639 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | D03 | | TB0205X | B035 | BJ | | 009 |
| 0639 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | D03 | | TB0205X | B036 | BJ | | 010-099 |
| 0641 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | A03 | | TB0205X | C036 | BJ | | 009 |
| 0641 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | A03 | | TB0205X | C036 | BJ | | 010-099 |
| 0642 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | K13 | | TB0205X | D036 | BJ | | 009 |
| 0642 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | K13 | | TB0205X | D036 | BJ | | 010-099 |
| 0643 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | H13 | | TB0205X | A037 | BJ | | 009 |
| 0643 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | H13 | | TB0205X | A037 | BJ | | 010-099 |
| 0643 | 22 | | PA | | 0-12 | 22-11-32 | D00055B | | J14 | | D00055B | H13 | | | 115-199 |
| 0644 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | C08 | | TB0205X | B037 | BJ | | 009 |
| 0644 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | C08 | | TB0205X | B037 | BJ | | 010-099 |
| 0645 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | D04 | | TB0205X | C037 | BJ | | 009 |
| 0645 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | D04 | | TB0205X | C037 | BJ | | 010-099 |
| 0646 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | J02 | | TB0205X | D038 | BJ | | 009 |
| 0646 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | J02 | | TB0205X | D038 | BJ | | 010-099 |
| 0647 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | G10 | | TB0205X | A039 | BJ | | 009 |
| 0647 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | G10 | | TB0205X | A039 | BJ | | 010-099 |
| 0648 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | J10 | | TB0205X | B039 | BJ | | 009 |
| 0648 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | J10 | | TB0205X | B039 | BJ | | 010-099 |
| 0649 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | G01 | | TB0205X | C039 | BJ | | 009 |
| 0649 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | G01 | | TB0205X | C039 | BJ | | 010-099 |
| 0650 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | H01 | | TB0205X | D039 | BJ | | 009 |
| 0650 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | H01 | | TB0205X | D039 | BJ | | 010-099 |
| 0651 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | A04 | | TB0205X | A044 | BJ | | 009 |
| 0651 | 22 | | GA | | 2-8 | 22-11-33 | D00055B | | A04 | | TB0205X | A044 | BJ | | 010-099 |
| 0652 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | F04 | | TB0205X | A030 | BJ | | 009 |
| 0652 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | F04 | | TB0205X | A030 | BJ | | 010-099 |
| 0653 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | B15 | | TB0205X | B030 | BJ | | 009 |
| 0653 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | B15 | | TB0205X | B030 | BJ | | 010-099 |
| 0654 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | D15 | | TB0205X | C030 | BJ | | 009 |
| 0654 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | D15 | | TB0205X | C030 | BJ | | 010-099 |
| 0655 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | | E05 | | TB0205X | D030 | BJ | | 009 |
| 0655 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | | E05 | | TB0205X | D030 | BJ | | 010-099 |
| 0656 | 20 | | GA | | 3-4 | 34-46-14 | D23005J | | | GX | GD02104 | ST.. | 2 | | 002 |
| 0657 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | | A14 | | TB0205X | C047 | BJ | | 009 |
| 0657 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | | A14 | | TB0205X | C047 | BJ | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 121

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | | 286N1175 | | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | |
| 0658 | 22 | GA | | | 4-0 | 34-46-13 | D00433B | | B14 | | TB0205X | D047 | BJ | | 009 |
| 0658 | 22 | GA | | | 2-7 | 34-46-13 | D00433B | | B14 | | TB0205X | D047 | BJ | | 010-099 |
| 0659 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | J08 | | TB0205X | C032 | BJ | | 009 |
| 0659 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | J08 | | TB0205X | C032 | BJ | | 010-099 |
| 0659 | 22 | PA | | | 0-12 | 22-11-32 | D00055B | | C11 | | D00055B | J08 | | | 115-199 |
| 0660 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | K09 | | TB0205X | D032 | BJ | | 009 |
| 0660 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | K09 | | TB0205X | D032 | BJ | | 010-099 |
| 0661 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | D14 | | TB0205X | A034 | BJ | | 009 |
| 0661 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | D14 | | TB0205X | A034 | BJ | | 010-099 |
| 0662 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | K07 | | TB0205X | B034 | BJ | | 009 |
| 0662 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | K07 | | TB0205X | B034 | BJ | | 010-099 |
| 0663 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | J15 | | TB0205X | C034 | BJ | | 009 |
| 0663 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | J15 | | TB0205X | C034 | BJ | | 010-099 |
| 0664 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | H14 | | TB0205X | D034 | BJ | | 009 |
| 0664 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | H14 | | TB0205X | D034 | BJ | | 010-099 |
| 0665 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | C14 | | TB0205X | A036 | BJ | | 009 |
| 0665 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | C14 | | TB0205X | A036 | BJ | | 010-099 |
| 0666 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | K04 | | TB0205X | B036 | BJ | | 009 |
| 0666 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | K04 | | TB0205X | B036 | BJ | | 010-099 |
| 0667 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | E04 | | TB0205X | C036 | BJ | | 009 |
| 0667 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | E04 | | TB0205X | C036 | BJ | | 010-099 |
| 0668 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | K14 | | TB0205X | D036 | BJ | | 009 |
| 0668 | 22 | GA | | | 3-1 | 22-11-33 | D00055B | | K14 | | TB0205X | D036 | BJ | | 010-099 |
| 0669 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | J14 | | TB0205X | A038 | BJ | | 009 |
| 0669 | 22 | GA | | | 2-8 | 22-11-33 | D00055B | | J14 | | TB0205X | A038 | BJ | | 010-099 |
| 0670 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | E08 | | TB0205X | B038 | BJ | | 009 |
| 0670 | 22 | GA | | | 2-8 | 22-11-33 | D00055B | | E08 | | TB0205X | B038 | BJ | | 010-099 |
| 0671 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | H04 | | TB0205X | C038 | BJ | | 009 |
| 0671 | 22 | GA | | | 2-8 | 22-11-33 | D00055B | | H04 | | TB0205X | C038 | BJ | | 010-099 |
| 0672 | 22 | GA | | | 4-0 | 22-11-33 | D00055B | | J04 | | TB0205X | D038 | BJ | | 009 |
| 0672 | 22 | GA | | | 2-8 | 22-11-33 | D00055B | | J04 | | TB0205X | D038 | BJ | | 010-099 |
| 0673 | 22 | GA | | | 4-0 | 22-11-33 | D00055A | | G08 | | TB0205X | A040 | BJ | | 009 |
| 0673 | 22 | GA | | | 2-9 | 22-11-33 | D00055A | | G08 | | TB0205X | A040 | BJ | | 010-099 |
| 0674 | 22 | GA | | | 4-0 | 22-11-33 | D00055A | | E10 | | TB0205X | B040 | BJ | | 009 |
| 0674 | 22 | GA | | | 2-9 | 22-11-33 | D00055A | | E10 | | TB0205X | B040 | BJ | | 010-099 |
| 0675 | 22 | GA | | | 4-0 | 22-11-33 | D00055A | | G02 | | TB0205X | C040 | BJ | | 009 |
| 0675 | 22 | GA | | | 2-9 | 22-11-33 | D00055A | | G02 | | TB0205X | C040 | BJ | | 010-099 |
| 0676 | 22 | GA | | | 4-0 | 22-11-33 | D00055A | | H02 | | TB0205X | D040 | BJ | | 009 |
| 0676 | 22 | GA | | | 2-9 | 22-11-33 | D00055A | | H02 | | TB0205X | D040 | BJ | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 122

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 0677 | 22 | | GA | | 4-0 | 22-11-33 | D00055A | D04 | | | TB0205X | A044 | BJ | | 009 |
| 0677 | 22 | | GA | | 2-9 | 22-11-33 | D00055A | D04 | | | TB0205X | A044 | BJ | | 010-099 |
| 0678 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | A14 | | | TB0205X | A032 | BJ | | 009 |
| 0678 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | A14 | | | TB0205X | A032 | BJ | | 010-099 |
| 0679 | 22 | | GA | | 4-0 | 22-11-33 | D00055B | B14 | | | TB0205X | B032 | BJ | | 009 |
| 0679 | 22 | | GA | | 3-1 | 22-11-33 | D00055B | B14 | | | TB0205X | B032 | BJ | | 010-099 |
| 0680 | 20 | | GA | | 3-0 | 34-46-14 | D23003J | | | GZ | GD02102 | ST.. | 2 | | 002 |
| 0681 | 20 | | GA | | 5-0 | 34-46-14 | D41819J | | | EE | GD02107 | ST.. | 2 | | 002 |
| 0683 | 22 | | GA | | 5-0 | 34-46-11 | D42083J | 4 | | | D00433B | B14 | | | 002 |
| 0694 | 24 | | PK | | 4-9 | 34-22-37 | D00085D | J15 | | | D41605J | 49 | | | 115-199 |
| 0695 | 24 | | PK | | 4-9 | 34-22-37 | D00085A | G15 | | | D41605J | 36 | | | 115-199 |
| 0696 | 22 | | GA | | 5-0 | 34-46-14 | D41819J | 24 | | | TB0205Y | C042 | BJ | | 002 |
| 0697 | 20 | | GA | | 5-0 | 34-46-14 | D23005J | | | DJ | GD02117 | ST.. | 2 | | 002 |
| 0698 | 20 | | GA | | 3-0 | 34-46-14 | D23003J | | | DR | GD02105 | ST.. | 2 | | 002 |
| 0702 | 20 | | GA | | 2-1 | 31-31-42 | D41815J | | | LH | GD02107 | ST.. | 2 | | 001-099 |
| 0706 | 22 | | PA | | 2-0 | 34-61-15 | D41884J | 6 | | | D41433J | 35 | | | 115-199 |
| 0707 | 22 | | GA | | 2-7 | 34-25-11 | D00919A | C10 | | | GD02103 | ST.. | 2 | | 001, 003-099 |
| 0708 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | A04 | | | TB0205X | A052 | BJ | | 009 |
| 0708 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | A04 | | | TB0205X | A052 | BJ | | 010-099 |
| 0709 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | A02 | | | TB0205X | A048 | BJ | | 009 |
| 0709 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | A02 | | | TB0205X | A048 | BJ | | 010-099 |
| 0732 | 24 | | PK | | 3-0 | 34-22-37 | SM00073 | | 9 | | D42049J | 19 | | | 115-199 |
| 0733 | 24 | | PK | | 4-0 | 34-22-38 | SM00073 | | 9 | | D41815J | 48 | | | 115-199 |
| 0734 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | C04 | | | TB0205X | B052 | BJ | | 009-099 |
| 0735 | 22 | | GA | | 4-0 | 34-46-13 | D00433B | C14 | | | TB0205X | D053 | BJ | | 009 |
| 0735 | 22 | | GA | | 2-7 | 34-46-13 | D00433B | C14 | | | TB0205X | D053 | BJ | | 010-099 |
| 0736 | 22 | | GA | | 4-0 | 34-46-13 | D00433A | D11 | | | TB0205X | D045 | BJ | | 009 |
| 0736 | 22 | | GA | | 2-9 | 34-46-13 | D00433A | D11 | | | TB0205X | D045 | BJ | | 010-099 |
| 0743 | 24 | | GK | | 4-1 | 34-22-39 | D41433J | 26 | | | D00085D | G12 | | | 001-099 |
| 0771 | 22 | | GA | | 1-0 | 34-43-14 | TB0205Y | A095 | BJ | | TB0205A | C009 | 2 | | 002 |
| 0772 | 22 | | GA | | 3-0 | 34-46-11 | TB0205Z | 115 | BJ | | TB0205A | A010 | 2 | | 002 |
| 0773 | 22 | | GA | | 6-0 | 34-43-14 | TB0205Y | A095 | BJ | | TB0205Y | C078 | BJ | | 002 |
| 0796 | 22 | | GA | | 6-0 | 34-46-11 | TB0205Z | 91 | BJ | | TB0205A | C010 | 2 | | 002 |
| 0798 | 20 | | GA | | 1-6 | 34-46-12 | D41349J | | | IU | GD02105 | ST.. | 2 | | 002 |
| 0801 | 22 | | GA | | 4-0 | 34-46-12 | D41433J | 44 | | | D00433A | D12 | | | 002 |
| 1001 | 22 | | GT | GR | 2-0 | 22-14-11 | D41349J | 40 | | | SM00018 | | WI | | 115-199 |
| 1001Z | | | | GR | 0-0 | 22-14-11 | D41349J | DED | | | SM00018 | DED | | | 115-199 |
| 1002 | 22 | | GT | GS | 2-0 | 22-14-21 | D42167J | 2 | | | SM00013 | | WI | | 115-199 |
| 1002Z | | | | GS | 0-0 | 22-14-21 | D42167J | DED | | | SM00013 | DED | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 123

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 1003 | 20 | GT | GT | | 4-0 | 22-31-12 | D41884J | 10 | | | D00383C | 5 | | | 115-199 |
| 1003Z | | | GT | | 0-0 | 22-31-12 | D41884J | DED | | | D00383C | DED | | | 115-199 |
| 1004 | 22 | GT | GU | | 2-0 | 22-11-12 | D41643J | 22 | | | SM00014 | | WI | | 115-199 |
| 1004Z | | | GU | | 0-0 | 22-11-12 | D41643J | DED | | | SM00014 | DED | | | 115-199 |
| 1005 | 22 | GT | GV | | 2-0 | 22-11-12 | D41643J | 23 | | | SM00015 | | WI | | 115-199 |
| 1005Z | | | GV | | 0-0 | 22-11-12 | D41643J | DED | | | SM00015 | DED | | | 115-199 |
| 1006 | 22 | GT | GW | | 2-0 | 22-11-22 | D41433J | 28 | | | SM00013 | | WI | | 115-199 |
| 1006Z | | | GW | | 0-0 | 22-11-22 | D41433J | DED | | | SM00013 | DED | | | 115-199 |
| 1007 | 22 | GT | GX | | 2-0 | 22-11-22 | D41349J | 38 | | | SM00014 | | WI | | 115-199 |
| 1007Z | | | GX | | 0-0 | 22-11-22 | D41349J | DED | | | SM00014 | DED | | | 115-199 |
| 1008 | 22 | GT | GY | | 2-0 | 22-11-22 | D41349J | 39 | | | SM00015 | | WI | | 115-199 |
| 1008Z | | | GY | | 0-0 | 22-11-22 | D41349J | DED | | | SM00015 | DED | | | 115-199 |
| 1009 | 20 | GT | GZ | | 2-0 | 22-11-32 | D41884J | 11 | | | SM00013 | | WI | | 115-199 |
| 1009Z | | | GZ | | 0-0 | 22-11-32 | D41884J | DED | | | SM00013 | DED | | | 115-199 |
| 1010 | 20 | GT | HA | | 3-0 | 22-11-32 | SM00013 | | WI | | D00055C | 9 | | | 115-199 |
| 1010Z | | | HA | | 0-0 | 22-11-32 | SM00013 | DED | | | D00055C | DED | | | 115-199 |
| 1011 | 22 | GT | HB | | 2-0 | 22-14-11 | D41349J | 44 | | | SM00018 | | WI | | 115-199 |
| 1011Z | | | HB | | 0-0 | 22-14-11 | D41349J | DED | | | SM00018 | DED | | | 115-199 |
| 1012 | 22 | GT | HC | | 2-0 | 22-14-21 | D41605J | 40 | | | SM00018 | | WI | | 115-199 |
| 1012Z | | | HC | | 0-0 | 22-14-21 | D41605J | DED | | | SM00018 | DED | | | 115-199 |
| 1013 | 22 | GT | HD | | 2-0 | 22-14-21 | D41605J | 48 | | | SM00003 | | WI | | 115-199 |
| 1013Z | | | HD | | 0-0 | 22-14-21 | D41605J | DED | | | SM00003 | DED | | | 115-199 |
| 1014 | 22 | GT | HE | | 3-0 | 22-14-31 | D41349J | 42 | | | D00055A | F01 | | | 115-199 |
| 1014Z | | | HE | | 0-0 | 22-14-31 | D41349J | DED | | | D00055A | DED | | | 115-199 |
| 1015 | 22 | GT | HF | | 4-0 | 22-14-31 | D41643J | 3 | | | D00055B | K03 | | | 115-199 |
| 1015Z | | | HF | | 0-0 | 22-14-31 | D41643J | DED | | | D00055B | DED | | | 115-199 |
| 1016 | 22 | GT | HG | | 2-0 | 22-14-31 | D41395J | 33 | | | D00055B | G12 | | | 115-199 |
| 1016Z | | | HG | | 0-0 | 22-14-31 | D41395J | DED | | | D00055B | DED | | | 115-199 |
| 1017 | 22 | GT | HH | | 4-0 | 22-14-31 | D41643J | 20 | | | D00055A | F03 | | | 115-199 |
| 1017Z | | | HH | | 0-0 | 22-14-31 | D41643J | DED | | | D00055A | DED | | | 115-199 |
| 1018 | 22 | GT | HI | | 4-0 | 22-14-31 | D41643J | 21 | | | D00055B | E12 | | | 115-199 |
| 1018Z | | | HI | | 0-0 | 22-14-31 | D41643J | DED | | | D00055B | DED | | | 115-199 |
| 1019 | 22 | GT | HJ | | 3-0 | 22-14-31 | SM00018 | | WI | | D00055B | K02 | | | 115-199 |
| 1019Z | | | HJ | | 0-0 | 22-14-31 | SM00018 | DED | | | D00055B | DED | | | 115-199 |
| 1020 | 22 | GT | HK | | 4-0 | 22-15-12 | D00055A | K03 | | | D41567J | 47 | | | 115-199 |
| 1020Z | | | HK | | 0-0 | 22-15-12 | D00055A | DED | | | D41567J | DED | | | 115-199 |
| 1021 | 22 | GT | HL | | 3-0 | 22-15-12 | D00055A | K01 | | | D41605J | 41 | | | 115-199 |
| 1021Z | | | HL | | 0-0 | 22-15-12 | D00055A | DED | | | D41605J | DED | | | 115-199 |
| 1022 | 22 | GT | FE | | 4-0 | 22-41-13 | D00055B | F09 | | | D42167J | 3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 124

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 1022Z | | | | FE | 0-0 | 22-41-13 | D00055B | DED | | | D42167J | DED | | | 115-199 |
| 1023 | 22 | | GT | FM | 4-0 | 22-41-13 | D00055B | F10 | | | D42021J | 15 | | | 115-199 |
| 1023Z | | | | FM | 0-0 | 22-41-13 | D00055B | DED | | | D42021J | DED | | | 115-199 |
| 1024 | 22 | | GT | HO | 3-0 | 22-41-11 | D00055A | A03 | | | D41097J | 21 | | | 115-199 |
| 1024Z | | | | HO | 0-0 | 22-41-11 | D00055A | DED | | | D41097J | DED | | | 115-199 |
| 1025 | 22 | | GT | HP | 4-0 | 22-41-11 | D00383B | C15 | | | D41097J | 22 | | | 115-199 |
| 1025Z | | | | HP | 0-0 | 22-41-11 | D00383B | DED | | | D41097J | DED | | | 115-199 |
| 1026 | 22 | | GT | HQ | 3-0 | 22-15-12 | D00055A | G01 | | | D41349J | 31 | | | 115-199 |
| 1026Z | | | | HQ | 0-0 | 22-15-12 | D00055A | DED | | | D41349J | DED | | | 115-199 |
| 1027 | 22 | | GT | HR | 3-0 | 22-41-11 | D00055B | C06 | | | D41349J | 32 | | | 115-199 |
| 1027Z | | | | HR | 0-0 | 22-41-11 | D00055B | DED | | | D41349J | DED | | | 115-199 |
| 1028 | 24 | | G1 | IE | 5-0 | 73-21-22 | D41349J | 43 | | | D41784J | 2 | | | 115-199 |
| 1028Z | | | | IE | 0-0 | 73-21-22 | D41349J | DED | | | D41784J | DED | | | 115-199 |
| 1029 | 24 | | G1 | IF | 5-0 | 73-21-22 | D41349J | 45 | | | D41784J | 1 | | | 115-199 |
| 1029Z | | | | IF | 0-0 | 73-21-22 | D41349J | DED | | | D41784J | DED | | | 115-199 |
| 1151 | 22 | | GT | IG | 2-0 | 22-11-12 | D41433J | 27 | | | SM00013 | | WI | | 115-199 |
| 1151Z | | | | IG | 0-0 | 22-11-12 | D41433J | DED | | | SM00013 | DED | | | 115-199 |
| 2001B | 24 | | GL | GD | 3-9 | 34-24-11 | D00447A | B05 | | | D42049J | 13 | | | 001-099 |
| 2001B | 24 | | GL | GD | 4-0 | 34-24-11 | D42049J | 13 | | | D00447A | B05 | | | 115-199 |
| 2001R | 24 | | GL | GD | 0-0 | 34-24-11 | D00447A | A05 | | | D42049J | 12 | | | 001-099 |
| 2001R | 24 | | GL | GD | 0-0 | 34-24-11 | D42049J | 12 | | | D00447A | A05 | | | 115-199 |
| 2002B | 24 | | GL | GE | 3-9 | 34-24-11 | D00447A | F01 | | | D42049J | 7 | | | 001-099 |
| 2002B | 24 | | GL | GE | 4-0 | 34-24-11 | D42049J | 7 | | | D00447A | F01 | | | 115-199 |
| 2002R | 24 | | GL | GE | 0-0 | 34-24-11 | D00447A | E01 | | | D42049J | 6 | | | 001-099 |
| 2002R | 24 | | GL | GE | 0-0 | 34-24-11 | D42049J | 6 | | | D00447A | E01 | | | 115-199 |
| 2003B | 24 | | GL | GF | 3-9 | 34-24-11 | D00447A | J01 | | | D42049J | 9 | | | 001-099 |
| 2003B | 24 | | GL | GF | 4-0 | 34-24-11 | D42049J | 9 | | | D00447A | J01 | | | 115-199 |
| 2003R | 24 | | GL | GF | 0-0 | 34-24-11 | D00447A | H01 | | | D42049J | 8 | | | 001-099 |
| 2003R | 24 | | GL | GF | 0-0 | 34-24-11 | D42049J | 8 | | | D00447A | H01 | | | 115-199 |
| 2004B | 24 | | GL | GH | 3-9 | 34-24-11 | D00447A | B03 | | | D42049J | 11 | | | 001-099 |
| 2004B | 24 | | GL | GH | 4-0 | 34-24-11 | D42049J | 11 | | | D00447A | B03 | | | 115-199 |
| 2004R | 24 | | GL | GH | 0-0 | 34-24-11 | D00447A | A03 | | | D42049J | 10 | | | 001-099 |
| 2004R | 24 | | GL | GH | 0-0 | 34-24-11 | D42049J | 10 | | | D00447A | A03 | | | 115-199 |
| 2005B | 24 | | GL | GI | 3-9 | 34-24-11 | D00447A | E03 | | | D42049J | 5 | | | 001-099 |
| 2005B | 24 | | GL | GI | 4-0 | 34-24-11 | D42049J | 5 | | | D00447A | E03 | | | 115-199 |
| 2005R | 24 | | GL | GI | 0-0 | 34-24-11 | D00447A | D03 | | | D42049J | 4 | | | 001-099 |
| 2005R | 24 | | GL | GI | 0-0 | 34-24-11 | D42049J | 4 | | | D00447A | D03 | | | 115-199 |
| 2006B | 22 | | GB | GO | 2-4 | 34-31-31 | D00207B | C15 | | | D42109J | 8 | | | 001-099 |
| 2006B | 22 | | GB | GO | 2-0 | 34-31-31 | D42109J | 8 | | | D02943C | 6 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 125

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 2006R | 22 | GB | GO | | 0-0 | 34-31-31 | D00207B | B15 | | | D42109J | 9 | | | 001-099 |
| 2006R | 22 | GB | GO | | 0-0 | 34-31-31 | D42109J | 9 | | | D02943C | 4 | | | 115-199 |
| 2007B | 24 | GL | ET | | 2-6 | 22-33-11 | D00383A | G13 | | | D41784J | 8 | | | 001-099 |
| 2007B | 24 | GL | ET | | 3-0 | 22-33-11 | D00383A | G13 | | | D41784J | 8 | | | 115-199 |
| 2007R | 24 | GL | ET | | 0-0 | 22-33-11 | D00383A | G14 | | | D41784J | 7 | | | ALL |
| 2008B | 22 | GB | EU | | 4-6 | 22-33-11 | D41784J | 6 | | | SM00010 | | WI | | 001-099 |
| 2008B | 22 | GB | EU | | 4-0 | 22-33-11 | SM00010 | | WI | | D41784J | 6 | | | 115-199 |
| 2008R | 22 | GB | EU | | 0-0 | 22-33-11 | D41784J | 5 | | | SM00009 | | WI | | 001-099 |
| 2008R | 22 | GB | EU | | 0-0 | 22-33-11 | SM00009 | | WI | | D41784J | 5 | | | 115-199 |
| 2009B | 22 | GB | EV | | 4-5 | 22-33-11 | D41782J | 2 | | | SM00010 | | WI | | 001-099 |
| 2009B | 22 | GB | EV | | 4-0 | 22-33-11 | SM00010 | | WI | | D41782J | 2 | | | 115-199 |
| 2009R | 22 | GB | EV | | 0-0 | 22-33-11 | D41782J | 1 | | | SM00009 | | WI | | 001-099 |
| 2009R | 22 | GB | EV | | 0-0 | 22-33-11 | SM00009 | | WI | | D41782J | 1 | | | 115-199 |
| 2010B | 24 | GL | EW | | 2-4 | 22-33-11 | D00383B | J02 | | | D41782J | 3 | | | 001-099 |
| 2010B | 24 | GL | EW | | 2-0 | 22-33-11 | D00383B | J02 | | | D41782J | 3 | | | 115-199 |
| 2010R | 24 | GL | EW | | 0-0 | 22-33-11 | D00383B | J03 | | | D41782J | 4 | | | ALL |
| 2011B | 24 | GL | EX | | 4-3 | 22-32-13 | D00383B | J04 | | | D41097J | 18 | | | 001-099 |
| 2011B | 24 | GL | EX | | 4-0 | 22-32-13 | D41097J | 18 | | | D00383B | J04 | | | 115-199 |
| 2011R | 24 | GL | EX | | 0-0 | 22-32-13 | D00383B | K04 | | | D41097J | 17 | | | 001-099 |
| 2011R | 24 | GL | EX | | 0-0 | 22-32-13 | D41097J | 17 | | | D00383B | K04 | | | 115-199 |
| 2013B | 24 | GL | FB | | 2-7 | 22-32-13 | D00383A | K09 | | | D41711J | 11 | | | 001-099 |
| 2013B | 24 | GL | FB | | 3-0 | 22-32-13 | D41711J | 11 | | | D00383A | K09 | | | 115-199 |
| 2013R | 24 | GL | FB | | 0-0 | 22-32-13 | D00383A | J09 | | | D41711J | 12 | | | 001-099 |
| 2013R | 24 | GL | FB | | 0-0 | 22-32-13 | D41711J | 12 | | | D00383A | J09 | | | 115-199 |
| 2014B | 24 | GL | AJ | | 2-8 | 22-31-12 | D00383A | A15 | | | D42063J | 6 | | | 001-099 |
| 2014B | 24 | GL | AJ | | 3-0 | 22-31-12 | D42063J | 6 | | | D00383A | A15 | | | 115-199 |
| 2014R | 24 | GL | AJ | | 0-0 | 22-31-12 | D00383A | B15 | | | D42063J | 5 | | | 001-099 |
| 2014R | 24 | GL | AJ | | 0-0 | 22-31-12 | D42063J | 5 | | | D00383A | B15 | | | 115-199 |
| 2015B | 22 | GB | AK | | 2-8 | 22-31-12 | D00383A | A13 | | | D42063J | 8 | | | 001-099 |
| 2015B | 22 | GB | AK | | 3-0 | 22-31-12 | D42063J | 8 | | | D00383A | A13 | | | 115-199 |
| 2015R | 22 | GB | AK | | 0-0 | 22-31-12 | D00383A | A14 | | | D42063J | 7 | | | 001-099 |
| 2015R | 22 | GB | AK | | 0-0 | 22-31-12 | D42063J | 7 | | | D00383A | A14 | | | 115-199 |
| 2016B | 24 | GL | AL | | 2-7 | 22-31-12 | D00383B | A03 | | | D42063J | 10 | | | 001-099 |
| 2016B | 24 | GL | AL | | 3-0 | 22-31-12 | D42063J | 10 | | | D00383B | A03 | | | 115-199 |
| 2016R | 24 | GL | AL | | 0-0 | 22-31-12 | D00383B | A02 | | | D42063J | 9 | | | 001-099 |
| 2016R | 24 | GL | AL | | 0-0 | 22-31-12 | D42063J | 9 | | | D00383B | A02 | | | 115-199 |
| 2017B | 22 | GB | AM | | 4-8 | 22-31-11 | D00383B | K01 | | | SM00010 | | WI | | 001-099 |
| 2017B | 22 | GB | AM | | 4-0 | 22-31-11 | D00383B | K01 | | | SM00010 | | WI | | 115-199 |
| 2017R | 22 | GB | AM | | 0-0 | 22-31-11 | D00383B | K02 | | | SM00009 | | WI | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 126

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|-------------------------------------|------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 2018B | 22 | GB | JJ | | 2-8 | 34-31-11 | D42105J | | 8 | | | D00203B | C15 | | | 001-099 |
| 2018B | 22 | GB | JJ | | 4-0 | 34-31-11 | D42105J | | 8 | | | D02939C | 6 | | | 115-199 |
| 2018R | 22 | GB | JJ | | 0-0 | 34-31-11 | D42105J | | 9 | | | D00203B | B15 | | | 001-099 |
| 2018R | 22 | GB | JJ | | 0-0 | 34-31-11 | D42105J | | 9 | | | D02939C | 4 | | | 115-199 |
| 2019B | 20 | GB | FV | | 4-0 | 22-11-31 | TB0205Z | | 74 | BJ | | D00055C | 11 | | | 115-199 |
| 2019R | 20 | GB | FV | | 0-0 | 22-11-31 | TB0205Z | | 73 | BJ | | D00055C | 10 | | | 115-199 |
| 2020B | 22 | GB | FY | | 3-4 | 22-11-31 | D41695J | | 35 | | | TB0205Z | 74 | BJ | | 001-099 |
| 2020B | 22 | GB | FY | | 4-0 | 22-11-31 | TB0205Z | | 74 | BJ | | D41695J | 35 | | | 115-199 |
| 2020R | 22 | GB | FY | | 0-0 | 22-11-31 | D41695J | | 34 | | | TB0205Z | 73 | BJ | | 001-099 |
| 2020R | 22 | GB | FY | | 0-0 | 22-11-31 | TB0205Z | | 73 | BJ | | D41695J | 34 | | | 115-199 |
| 2021B | 22 | GB | FZ | | 2-2 | 22-11-31 | D41622J | | 15 | | | TB0205Z | 74 | BJ | | 001-099 |
| 2021B | 22 | GB | FZ | | 4-0 | 22-11-31 | TB0205Z | | 74 | BJ | | D41622J | 15 | | | 115-199 |
| 2021R | 22 | GB | FZ | | 0-0 | 22-11-31 | D41622J | | 16 | | | TB0205Z | 73 | BJ | | 001-099 |
| 2021R | 22 | GB | FZ | | 0-0 | 22-11-31 | TB0205Z | | 73 | BJ | | D41622J | 16 | | | 115-199 |
| 2022B | 22 | GB | FX | | 3-4 | 22-11-31 | D41695J | | 5 | | | TB0205Z | 74 | BJ | | 001-099 |
| 2022B | 22 | GB | FX | | 4-0 | 22-11-31 | TB0205Z | | 74 | BJ | | D41695J | 5 | | | 115-199 |
| 2022R | 22 | GB | FX | | 0-0 | 22-11-31 | D41695J | | 6 | | | TB0205Z | 73 | BJ | | 001-099 |
| 2022R | 22 | GB | FX | | 0-0 | 22-11-31 | TB0205Z | | 73 | BJ | | D41695J | 6 | | | 115-199 |
| 2023B | 22 | GB | FW | | 3-4 | 22-11-31 | D41695J | | 7 | | | TB0205Z | 74 | BJ | | 001-099 |
| 2023B | 22 | GB | FW | | 4-0 | 22-11-31 | TB0205Z | | 74 | BJ | | D41695J | 7 | | | 115-199 |
| 2023R | 22 | GB | FW | | 0-0 | 22-11-31 | D41695J | | 8 | | | TB0205Z | 73 | BJ | | 001-099 |
| 2023R | 22 | GB | FW | | 0-0 | 22-11-31 | TB0205Z | | 73 | BJ | | D41695J | 8 | | | 115-199 |
| 2024B | 22 | GB | DT | | 3-0 | 22-12-31 | D00055B | | D11 | | | D41695J | 9 | | | ALL |
| 2024R | 22 | GB | DT | | 0-0 | 22-12-31 | D00055B | | E11 | | | D41695J | 10 | | | ALL |
| 2025B | 22 | GB | EC | | 2-10 | 22-13-31 | D00055B | | E06 | | | D41622J | 18 | | | 001-099 |
| 2025B | 22 | GB | EC | | 4-0 | 22-13-31 | D00055B | | E06 | | | D41622J | 18 | | | 115-199 |
| 2025R | 22 | GB | EC | | 0-0 | 22-13-31 | D00055B | | F06 | | | D41622J | 17 | | | ALL |
| 2026B | 22 | GB | EG | | 3-0 | 22-13-31 | D00055B | | E07 | | | D41695J | 11 | | | ALL |
| 2026R | 22 | GB | EG | | 0-0 | 22-13-31 | D00055B | | F07 | | | D41695J | 12 | | | ALL |
| 2027B | 20 | GB | FO | | 3-10 | 29-32-41 | D41622J | | 20 | | | D41643J | 2 | | | 001-099 |
| 2027B | 20 | GB | FO | | 5-0 | 29-32-41 | D41643J | | 2 | | | D41622J | 20 | | | 115-199 |
| 2027R | 20 | GB | FO | | 0-0 | 29-32-41 | D41622J | | 19 | | | D41643J | 1 | | | 001-099 |
| 2027R | 20 | GB | FO | | 0-0 | 29-32-41 | D41643J | | 1 | | | D41622J | 19 | | | 115-199 |
| 2028B | 22 | GB | IB | | 2-4 | 22-12-31 | D00055B | | F13 | | | D41815J | 41 | | | 001-099 |
| 2028B | 22 | GB | IB | | 2-0 | 22-12-31 | D00055B | | F13 | | | D41815J | 41 | | | 115-199 |
| 2028R | 22 | GB | IB | | 0-0 | 22-12-31 | D00055B | | E13 | | | D41815J | 40 | | | ALL |
| 2036B | 20 | GB | FE | | 2-8 | 22-11-31 | D00055C | | 11 | | | TB0205Z | 74 | BJ | | 001-099 |
| 2036R | 20 | GB | FE | | 0-0 | 22-11-31 | D00055C | | 10 | | | TB0205Z | 73 | BJ | | 001-099 |
| 2501T | 24 | BV | BF | | 2-10 | 34-22-34 | D00085E | | J01 | | | D40883J | 1 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 127

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | To | | | | | | | | | | |
|------------|-------------|----|-------|-------------------------------------|------|----------|---------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 2501T | 24 | BV | BF | | 3-0 | 34-22-34 | D40883J | 1 | | | | D00085E | J01 | | | 115-199 |
| 2501W | 24 | BV | BF | | 0-0 | 34-22-34 | D00085E | K01 | | | | D40883J | 2 | | | 001-099 |
| 2501W | 24 | BV | BF | | 0-0 | 34-22-34 | D40883J | 2 | | | | D00085E | K01 | | | 115-199 |
| 2501Z | | | BF | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 3 | | | 001-099 |
| 2501Z | | | BF | | 0-0 | 34-22-34 | D40883J | 3 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2502T | 24 | BV | BG | | 2-10 | 34-22-34 | D00085E | J02 | | | | D40883J | 4 | | | 001-099 |
| 2502T | 24 | BV | BG | | 3-0 | 34-22-34 | D40883J | 4 | | | | D00085E | J02 | | | 115-199 |
| 2502W | 24 | BV | BG | | 0-0 | 34-22-34 | D00085E | K02 | | | | D40883J | 5 | | | 001-099 |
| 2502W | 24 | BV | BG | | 0-0 | 34-22-34 | D40883J | 5 | | | | D00085E | K02 | | | 115-199 |
| 2502Z | | | BG | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 6 | | | 001-099 |
| 2502Z | | | BG | | 0-0 | 34-22-34 | D40883J | 6 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2503T | 24 | BV | BH | | 2-10 | 34-22-34 | D00085E | J03 | | | | D40883J | 7 | | | 001-099 |
| 2503T | 24 | BV | BH | | 3-0 | 34-22-34 | D40883J | 7 | | | | D00085E | J03 | | | 115-199 |
| 2503W | 24 | BV | BH | | 0-0 | 34-22-34 | D00085E | K03 | | | | D40883J | 8 | | | 001-099 |
| 2503W | 24 | BV | BH | | 0-0 | 34-22-34 | D40883J | 8 | | | | D00085E | K03 | | | 115-199 |
| 2503Z | | | BH | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 9 | | | 001-099 |
| 2503Z | | | BH | | 0-0 | 34-22-34 | D40883J | 9 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2504T | 24 | BV | BI | | 2-10 | 34-22-34 | D00085E | J04 | | | | D40883J | 10 | | | 001-099 |
| 2504T | 24 | BV | BI | | 3-0 | 34-22-34 | D40883J | 10 | | | | D00085E | J04 | | | 115-199 |
| 2504W | 24 | BV | BI | | 0-0 | 34-22-34 | D00085E | K04 | | | | D40883J | 11 | | | 001-099 |
| 2504W | 24 | BV | BI | | 0-0 | 34-22-34 | D40883J | 11 | | | | D00085E | K04 | | | 115-199 |
| 2504Z | | | BI | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 12 | | | 001-099 |
| 2504Z | | | BI | | 0-0 | 34-22-34 | D40883J | 12 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2505T | 24 | BV | BJ | | 2-10 | 34-22-34 | D00085E | J05 | | | | D40883J | 13 | | | 001-099 |
| 2505T | 24 | BV | BJ | | 3-0 | 34-22-34 | D40883J | 13 | | | | D00085E | J05 | | | 115-199 |
| 2505W | 24 | BV | BJ | | 0-0 | 34-22-34 | D00085E | K05 | | | | D40883J | 14 | | | 001-099 |
| 2505W | 24 | BV | BJ | | 0-0 | 34-22-34 | D40883J | 14 | | | | D00085E | K05 | | | 115-199 |
| 2505Z | | | BJ | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 15 | | | 001-099 |
| 2505Z | | | BJ | | 0-0 | 34-22-34 | D40883J | 15 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2506T | 24 | BV | BK | | 2-10 | 34-22-34 | D00085E | J06 | | | | D40883J | 16 | | | 001-099 |
| 2506T | 24 | BV | BK | | 3-0 | 34-22-34 | D40883J | 16 | | | | D00085E | J06 | | | 115-199 |
| 2506W | 24 | BV | BK | | 0-0 | 34-22-34 | D00085E | K06 | | | | D40883J | 17 | | | 001-099 |
| 2506W | 24 | BV | BK | | 0-0 | 34-22-34 | D40883J | 17 | | | | D00085E | K06 | | | 115-199 |
| 2506Z | | | BK | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 18 | | | 001-099 |
| 2506Z | | | BK | | 0-0 | 34-22-34 | D40883J | 18 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2507T | 24 | BV | BL | | 2-10 | 34-22-34 | D00085E | J07 | | | | D40883J | 19 | | | 001-099 |
| 2507T | 24 | BV | BL | | 3-0 | 34-22-34 | D40883J | 19 | | | | D00085E | J07 | | | 115-199 |
| 2507W | 24 | BV | BL | | 0-0 | 34-22-34 | D00085E | K07 | | | | D40883J | 20 | | | 001-099 |
| 2507W | 24 | BV | BL | | 0-0 | 34-22-34 | D40883J | 20 | | | | D00085E | K07 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 128

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1175 | 286N1175 | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | | |
| 2507Z | | BL | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | D40883J | 21 | | | 001-099 | | |
| 2507Z | | BL | 0-0 | 34-22-34 | D40883J | 21 | | | GD02119 | ST.. | 2 | | 115-199 | | |
| 2508T | 24 | BV BM | 2-10 | 34-22-34 | D00085E | J08 | | | D40883J | 22 | | | 001-099 | | |
| 2508T | 24 | BV BM | 3-0 | 34-22-34 | D40883J | 22 | | | D00085E | J08 | | | 115-199 | | |
| 2508W | 24 | BV BM | 0-0 | 34-22-34 | D00085E | K08 | | | D40883J | 23 | | | 001-099 | | |
| 2508W | 24 | BV BM | 0-0 | 34-22-34 | D40883J | 23 | | | D00085E | K08 | | | 115-199 | | |
| 2508Z | | BM | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | D40883J | 24 | | | 001-099 | | |
| 2508Z | | BM | 0-0 | 34-22-34 | D40883J | 24 | | | GD02119 | ST.. | 2 | | 115-199 | | |
| 2509T | 24 | BV BN | 2-10 | 34-22-34 | D00085E | J09 | | | D40883J | 25 | | | 001-099 | | |
| 2509T | 24 | BV BN | 3-0 | 34-22-34 | D40883J | 25 | | | D00085E | J09 | | | 115-199 | | |
| 2509W | 24 | BV BN | 0-0 | 34-22-34 | D00085E | K09 | | | D40883J | 26 | | | 001-099 | | |
| 2509W | 24 | BV BN | 0-0 | 34-22-34 | D40883J | 26 | | | D00085E | K09 | | | 115-199 | | |
| 2509Z | | BN | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | D40883J | 27 | | | 001-099 | | |
| 2509Z | | BN | 0-0 | 34-22-34 | D40883J | 27 | | | GD02119 | ST.. | 2 | | 115-199 | | |
| 2510T | 24 | BV BO | 2-10 | 34-22-34 | D00085E | G01 | | | D40883J | 28 | | | 001-099 | | |
| 2510T | 24 | BV BO | 3-0 | 34-22-34 | D40883J | 28 | | | D00085E | G01 | | | 115-199 | | |
| 2510W | 24 | BV BO | 0-0 | 34-22-34 | D00085E | H01 | | | D40883J | 29 | | | 001-099 | | |
| 2510W | 24 | BV BO | 0-0 | 34-22-34 | D40883J | 29 | | | D00085E | H01 | | | 115-199 | | |
| 2510Z | | BO | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | D40883J | 30 | | | 001-099 | | |
| 2510Z | | BO | 0-0 | 34-22-34 | D40883J | 30 | | | GD02119 | ST.. | 2 | | 115-199 | | |
| 2511T | 24 | BV BP | 2-10 | 34-22-34 | D00085E | G02 | | | D40883J | 31 | | | 001-099 | | |
| 2511T | 24 | BV BP | 3-0 | 34-22-34 | D40883J | 31 | | | D00085E | G02 | | | 115-199 | | |
| 2511W | 24 | BV BP | 0-0 | 34-22-34 | D00085E | H02 | | | D40883J | 32 | | | 001-099 | | |
| 2511W | 24 | BV BP | 0-0 | 34-22-34 | D40883J | 32 | | | D00085E | H02 | | | 115-199 | | |
| 2511Z | | BP | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | D40883J | 33 | | | 001-099 | | |
| 2511Z | | BP | 0-0 | 34-22-34 | D40883J | 33 | | | GD02119 | ST.. | 2 | | 115-199 | | |
| 2512T | 24 | BV BQ | 2-10 | 34-22-34 | D00085E | G03 | | | D40883J | 34 | | | 001-099 | | |
| 2512T | 24 | BV BQ | 3-0 | 34-22-34 | D40883J | 34 | | | D00085E | G03 | | | 115-199 | | |
| 2512W | 24 | BV BQ | 0-0 | 34-22-34 | D00085E | H03 | | | D40883J | 35 | | | 001-099 | | |
| 2512W | 24 | BV BQ | 0-0 | 34-22-34 | D40883J | 35 | | | D00085E | H03 | | | 115-199 | | |
| 2512Z | | BQ | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | D40883J | 36 | | | 001-099 | | |
| 2512Z | | BQ | 0-0 | 34-22-34 | D40883J | 36 | | | GD02119 | ST.. | 2 | | 115-199 | | |
| 2513T | 24 | BV BR | 2-10 | 34-22-34 | D00085E | G04 | | | D40883J | 37 | | | 001-099 | | |
| 2513T | 24 | BV BR | 3-0 | 34-22-34 | D40883J | 37 | | | D00085E | G04 | | | 115-199 | | |
| 2513W | 24 | BV BR | 0-0 | 34-22-34 | D00085E | H04 | | | D40883J | 38 | | | 001-099 | | |
| 2513W | 24 | BV BR | 0-0 | 34-22-34 | D40883J | 38 | | | D00085E | H04 | | | 115-199 | | |
| 2513Z | | BR | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | D40883J | 39 | | | 001-099 | | |
| 2513Z | | BR | 0-0 | 34-22-34 | D40883J | 39 | | | GD02119 | ST.. | 2 | | 115-199 | | |
| 2514T | 24 | BV BS | 2-10 | 34-22-34 | D00085E | G05 | | | D40883J | 40 | | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 129

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 2514T | 24 | BV | BS | | 3-0 | 34-22-34 | D40883J | 40 | | | | D00085E | G05 | | | 115-199 |
| 2514W | 24 | BV | BS | | 0-0 | 34-22-34 | D00085E | H05 | | | | D40883J | 41 | | | 001-099 |
| 2514W | 24 | BV | BS | | 0-0 | 34-22-34 | D40883J | 41 | | | | D00085E | H05 | | | 115-199 |
| 2514Z | | | BS | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 42 | | | 001-099 |
| 2514Z | | | BS | | 0-0 | 34-22-34 | D40883J | 42 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2515T | 24 | BV | BT | | 2-10 | 34-22-34 | D00085E | G06 | | | | D40883J | 43 | | | 001-099 |
| 2515T | 24 | BV | BT | | 3-0 | 34-22-34 | D40883J | 43 | | | | D00085E | G06 | | | 115-199 |
| 2515W | 24 | BV | BT | | 0-0 | 34-22-34 | D00085E | H06 | | | | D40883J | 44 | | | 001-099 |
| 2515W | 24 | BV | BT | | 0-0 | 34-22-34 | D40883J | 44 | | | | D00085E | H06 | | | 115-199 |
| 2515Z | | | BT | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 45 | | | 001-099 |
| 2515Z | | | BT | | 0-0 | 34-22-34 | D40883J | 45 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2516T | 24 | BV | BU | | 2-10 | 34-22-34 | D00085E | G07 | | | | D40883J | 46 | | | 001-099 |
| 2516T | 24 | BV | BU | | 3-0 | 34-22-34 | D40883J | 46 | | | | D00085E | G07 | | | 115-199 |
| 2516W | 24 | BV | BU | | 0-0 | 34-22-34 | D00085E | H07 | | | | D40883J | 47 | | | 001-099 |
| 2516W | 24 | BV | BU | | 0-0 | 34-22-34 | D40883J | 47 | | | | D00085E | H07 | | | 115-199 |
| 2516Z | | | BU | | 0-0 | 34-22-34 | GD02119 | ST.. | 2 | | | D40883J | 48 | | | 001-099 |
| 2516Z | | | BU | | 0-0 | 34-22-34 | D40883J | 48 | | | | GD02119 | ST.. | 2 | | 115-199 |
| 2517T | 24 | BV | BV | | 2-10 | 34-22-34 | D00085E | G08 | | | | D40883J | 49 | | | 001-099 |
| 2517T | 24 | BV | BV | | 3-0 | 34-22-34 | D40883J | 49 | | | | D00085E | G08 | | | 115-199 |
| 2517W | 24 | BV | BV | | 0-0 | 34-22-34 | D00085E | H08 | | | | D40883J | 50 | | | 001-099 |
| 2517W | 24 | BV | BV | | 0-0 | 34-22-34 | D40883J | 50 | | | | D00085E | H08 | | | 115-199 |
| 2517Z | | | BV | | 0-0 | 34-22-34 | GD02118 | ST.. | 2 | | | D40883J | 51 | | | 001-099 |
| 2517Z | | | BV | | 0-0 | 34-22-34 | D40883J | 51 | | | | GD02118 | ST.. | 2 | | 115-199 |
| 2518T | 24 | BV | BW | | 2-10 | 34-22-34 | D00085E | G09 | | | | D40883J | 52 | | | 001-099 |
| 2518T | 24 | BV | BW | | 3-0 | 34-22-34 | D40883J | 52 | | | | D00085E | G09 | | | 115-199 |
| 2518W | 24 | BV | BW | | 0-0 | 34-22-34 | D00085E | H09 | | | | D40883J | 53 | | | 001-099 |
| 2518W | 24 | BV | BW | | 0-0 | 34-22-34 | D40883J | 53 | | | | D00085E | H09 | | | 115-199 |
| 2518Z | | | BW | | 0-0 | 34-22-34 | GD02118 | ST.. | 2 | | | D40883J | 54 | | | 001-099 |
| 2518Z | | | BW | | 0-0 | 34-22-34 | D40883J | 54 | | | | GD02118 | ST.. | 2 | | 115-199 |
| 2519T | 24 | BV | BY | | 2-11 | 34-22-35 | D00085E | A01 | | | | D41087J | 1 | | | 001-099 |
| 2519T | 24 | BV | BY | | 3-0 | 34-22-35 | D41087J | 1 | | | | D00085E | A01 | | | 115-199 |
| 2519W | 24 | BV | BY | | 0-0 | 34-22-35 | D00085E | B01 | | | | D41087J | 2 | | | 001-099 |
| 2519W | 24 | BV | BY | | 0-0 | 34-22-35 | D41087J | 2 | | | | D00085E | B01 | | | 115-199 |
| 2519Z | | | BY | | 0-0 | 34-22-35 | GD02118 | ST.. | 2 | | | D41087J | 3 | | | 001-099 |
| 2519Z | | | BY | | 0-0 | 34-22-35 | D41087J | 3 | | | | GD02118 | ST.. | 2 | | 115-199 |
| 2520T | 24 | BV | BZ | | 2-11 | 34-22-35 | D00085E | A02 | | | | D41087J | 4 | | | 001-099 |
| 2520T | 24 | BV | BZ | | 3-0 | 34-22-35 | D41087J | 4 | | | | D00085E | A02 | | | 115-199 |
| 2520W | 24 | BV | BZ | | 0-0 | 34-22-35 | D00085E | B02 | | | | D41087J | 5 | | | 001-099 |
| 2520W | 24 | BV | BZ | | 0-0 | 34-22-35 | D41087J | 5 | | | | D00085E | B02 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 130

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1170
Page 131
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 2527T | 24 | BV | CG | | 3-0 | 34-22-35 | D41087J | 25 | | | D00085E | A09 | | | 115-199 |
| 2527W | 24 | BV | CG | | 0-0 | 34-22-35 | D00085E | B09 | | | D41087J | 26 | | | 001-099 |
| 2527W | 24 | BV | CG | | 0-0 | 34-22-35 | D41087J | 26 | | | D00085E | B09 | | | 115-199 |
| 2527Z | | | CG | | 0-0 | 34-22-35 | GD02118 | ST.. | 2 | | D41087J | 27 | | | 001-099 |
| 2527Z | | | CG | | 0-0 | 34-22-35 | D41087J | 27 | | | GD02118 | ST.. | 2 | | 115-199 |
| 2528T | 24 | BV | CH | | 2-11 | 34-22-35 | D00085E | C01 | | | D41087J | 28 | | | 001-099 |
| 2528T | 24 | BV | CH | | 3-0 | 34-22-35 | D41087J | 28 | | | D00085E | C01 | | | 115-199 |
| 2528W | 24 | BV | CH | | 0-0 | 34-22-35 | D00085E | D01 | | | D41087J | 29 | | | 001-099 |
| 2528W | 24 | BV | CH | | 0-0 | 34-22-35 | D41087J | 29 | | | D00085E | D01 | | | 115-199 |
| 2528Z | | | CH | | 0-0 | 34-22-35 | GD02118 | ST.. | 2 | | D41087J | 30 | | | 001-099 |
| 2528Z | | | CH | | 0-0 | 34-22-35 | D41087J | 30 | | | GD02118 | ST.. | 2 | | 115-199 |
| 2529T | 24 | BV | CI | | 2-11 | 34-22-35 | D00085E | C02 | | | D41087J | 31 | | | 001-099 |
| 2529T | 24 | BV | CI | | 3-0 | 34-22-35 | D41087J | 31 | | | D00085E | C02 | | | 115-199 |
| 2529W | 24 | BV | CI | | 0-0 | 34-22-35 | D00085E | D02 | | | D41087J | 32 | | | 001-099 |
| 2529W | 24 | BV | CI | | 0-0 | 34-22-35 | D41087J | 32 | | | D00085E | D02 | | | 115-199 |
| 2529Z | | | CI | | 0-0 | 34-22-35 | GD02118 | ST.. | 2 | | D41087J | 33 | | | 001-099 |
| 2529Z | | | CI | | 0-0 | 34-22-35 | D41087J | 33 | | | GD02118 | ST.. | 2 | | 115-199 |
| 2530T | 24 | BV | CJ | | 2-11 | 34-22-35 | D00085E | C03 | | | D41087J | 34 | | | 001-099 |
| 2530T | 24 | BV | CJ | | 3-0 | 34-22-35 | D41087J | 34 | | | D00085E | C03 | | | 115-199 |
| 2530W | 24 | BV | CJ | | 0-0 | 34-22-35 | D00085E | D03 | | | D41087J | 35 | | | 001-099 |
| 2530W | 24 | BV | CJ | | 0-0 | 34-22-35 | D41087J | 35 | | | D00085E | D03 | | | 115-199 |
| 2530Z | | | CJ | | 0-0 | 34-22-35 | GD02118 | ST.. | 2 | | D41087J | 36 | | | 001-099 |
| 2530Z | | | CJ | | 0-0 | 34-22-35 | D41087J | 36 | | | GD02118 | ST.. | 2 | | 115-199 |
| 2531T | 24 | BV | CK | | 2-11 | 34-22-35 | D00085E | C04 | | | D41087J | 37 | | | 001-099 |
| 2531T | 24 | BV | CK | | 3-0 | 34-22-35 | D41087J | 37 | | | D00085E | C04 | | | 115-199 |
| 2531W | 24 | BV | CK | | 0-0 | 34-22-35 | D00085E | D04 | | | D41087J | 38 | | | 001-099 |
| 2531W | 24 | BV | CK | | 0-0 | 34-22-35 | D41087J | 38 | | | D00085E | D04 | | | 115-199 |
| 2531Z | | | CK | | 0-0 | 34-22-35 | GD02118 | ST.. | 2 | | D41087J | 39 | | | 001-099 |
| 2531Z | | | CK | | 0-0 | 34-22-35 | D41087J | 39 | | | GD02118 | ST.. | 2 | | 115-199 |
| 2532T | 24 | BV | CL | | 2-11 | 34-22-35 | D00085E | C05 | | | D41087J | 40 | | | 001-099 |
| 2532T | 24 | BV | CL | | 3-0 | 34-22-35 | D41087J | 40 | | | D00085E | C05 | | | 115-199 |
| 2532W | 24 | BV | CL | | 0-0 | 34-22-35 | D00085E | D05 | | | D41087J | 41 | | | 001-099 |
| 2532W | 24 | BV | CL | | 0-0 | 34-22-35 | D41087J | 41 | | | D00085E | D05 | | | 115-199 |
| 2532Z | | | CL | | 0-0 | 34-22-35 | GD02118 | ST.. | 2 | | D41087J | 42 | | | 001-099 |
| 2532Z | | | CL | | 0-0 | 34-22-35 | D41087J | 42 | | | GD02118 | ST.. | 2 | | 115-199 |
| 2533T | 24 | BV | CM | | 2-11 | 34-22-35 | D00085E | C06 | | | D41087J | 43 | | | 001-099 |
| 2533T | 24 | BV | CM | | 3-0 | 34-22-35 | D41087J | 43 | | | D00085E | C06 | | | 115-199 |
| 2533W | 24 | BV | CM | | 0-0 | 34-22-35 | D00085E | D06 | | | D41087J | 44 | | | 001-099 |
| 2533W | 24 | BV | CM | | 0-0 | 34-22-35 | D41087J | 44 | | | D00085E | D06 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 132

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 2533Z | | | | CM | 0-0 | 34-22-35 | GD02117 | ST.. | 2 | | D41087J | 45 | | | 001-099 |
| 2533Z | | | | CM | 0-0 | 34-22-35 | D41087J | 45 | | | GD02117 | ST.. | 2 | | 115-199 |
| 2534T | 24 | BV | CN | | 2-11 | 34-22-35 | D00085E | C07 | | | D41087J | 46 | | | 001-099 |
| 2534T | 24 | BV | CN | | 3-0 | 34-22-35 | D41087J | 46 | | | D00085E | C07 | | | 115-199 |
| 2534W | 24 | BV | CN | | 0-0 | 34-22-35 | D00085E | D07 | | | D41087J | 47 | | | 001-099 |
| 2534W | 24 | BV | CN | | 0-0 | 34-22-35 | D41087J | 47 | | | D00085E | D07 | | | 115-199 |
| 2534Z | | | | CN | 0-0 | 34-22-35 | GD02117 | ST.. | 2 | | D41087J | 48 | | | 001-099 |
| 2534Z | | | | CN | 0-0 | 34-22-35 | D41087J | 48 | | | GD02117 | ST.. | 2 | | 115-199 |
| 2535T | 24 | BV | CO | | 2-11 | 34-22-35 | D00085E | C08 | | | D41087J | 49 | | | 001-099 |
| 2535T | 24 | BV | CO | | 3-0 | 34-22-35 | D41087J | 49 | | | D00085E | C08 | | | 115-199 |
| 2535W | 24 | BV | CO | | 0-0 | 34-22-35 | D00085E | D08 | | | D41087J | 50 | | | 001-099 |
| 2535W | 24 | BV | CO | | 0-0 | 34-22-35 | D41087J | 50 | | | D00085E | D08 | | | 115-199 |
| 2535Z | | | | CO | 0-0 | 34-22-35 | GD02117 | ST.. | 2 | | D41087J | 51 | | | 001-099 |
| 2535Z | | | | CO | 0-0 | 34-22-35 | D41087J | 51 | | | GD02117 | ST.. | 2 | | 115-199 |
| 2536T | 24 | BV | CP | | 2-11 | 34-22-35 | D00085E | C09 | | | D41087J | 52 | | | 001-099 |
| 2536T | 24 | BV | CP | | 3-0 | 34-22-35 | D41087J | 52 | | | D00085E | C09 | | | 115-199 |
| 2536W | 24 | BV | CP | | 0-0 | 34-22-35 | D00085E | D09 | | | D41087J | 53 | | | 001-099 |
| 2536W | 24 | BV | CP | | 0-0 | 34-22-35 | D41087J | 53 | | | D00085E | D09 | | | 115-199 |
| 2536Z | | | | CP | 0-0 | 34-22-35 | GD02117 | ST.. | 2 | | D41087J | 54 | | | 001-099 |
| 2536Z | | | | CP | 0-0 | 34-22-35 | D41087J | 54 | | | GD02117 | ST.. | 2 | | 115-199 |
| 2537B | 24 | G2 | GP | | 2-4 | 22-32-12 | D00383A | D04 | | | TB0205X | A120 | BJ | | 001-099 |
| 2537B | 24 | G2 | GP | | 4-0 | 22-32-12 | D00383A | D04 | | | TB0205X | A120 | BJ | | 115-199 |
| 2537R | 24 | G2 | GP | | 0-0 | 22-32-12 | D00383A | D03 | | | TB0205X | A119 | BJ | | ALL |
| 2537Z | | | | GP | 0-0 | 22-32-12 | D00383A | DED | | | GD02115 | ST.. | 2 | | ALL |
| 2538B | 24 | G2 | FS | | 2-11 | 23-51-13 | D00207B | B01 | | | D41433J | 23 | | | 001-099 |
| 2538B | 24 | G2 | FS | | 3-0 | 23-51-13 | D02943B | K10 | | | D41433J | 22 | | | 115-199 |
| 2538R | 24 | G2 | FS | | 0-0 | 23-51-13 | D00207B | A01 | | | D41433J | 22 | | | 001-099 |
| 2538R | 24 | G2 | FS | | 0-0 | 23-51-13 | D02943B | J10 | | | D41433J | 23 | | | 115-199 |
| 2538Z | | | | FS | 0-0 | 23-51-13 | D00207B | DED | | | D41433J | 24 | | | 001-099 |
| 2538Z | | | | FS | 0-0 | 23-51-13 | D02943B | DED | | | D41433J | 24 | | | 115-199 |
| 2539B | 24 | G2 | JG | | 2-9 | 23-51-13 | D41643J | 30 | | | D00203B | B01 | | | 001-099 |
| 2539B | 24 | G2 | LD | | 3-0 | 23-51-13 | D41643J | 30 | | | D02939B | K10 | | | 115-199 |
| 2539R | 24 | G2 | JG | | 0-0 | 23-51-13 | D41643J | 29 | | | D00203B | A01 | | | 001-099 |
| 2539R | 24 | G2 | LD | | 0-0 | 23-51-13 | D41643J | 29 | | | D02939B | J10 | | | 115-199 |
| 2539Z | | | | JG | 0-0 | 23-51-13 | D41643J | 31 | | | D00203B | DED | | | 001-099 |
| 2539Z | | | | LD | 0-0 | 23-51-13 | D41643J | 31 | | | D02939B | DED | | | 115-199 |
| 3002B | 22 | GC | FA | | 2-7 | 22-32-13 | D00383A | A11 | | | D41711J | 15 | | | 001-099 |
| 3002B | 22 | GC | FA | | 3-0 | 22-32-13 | D41711J | 15 | | | D00383A | A11 | | | 115-199 |
| 3002R | 22 | GC | FA | | 0-0 | 22-32-13 | D00383A | A12 | | | D41711J | 16 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 133

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 3002R | 22 | GC | FA | | 0-0 | 22-32-13 | D41711J | 16 | | | D00383A | A12 | | | 115-199 |
| 3002Y | 22 | GC | FA | | 0-0 | 22-32-13 | D00383A | A10 | | | D41711J | 17 | | | 001-099 |
| 3002Y | 22 | GC | FA | | 0-0 | 22-32-13 | D41711J | 17 | | | D00383A | A10 | | | 115-199 |
| 3003B | 22 | GC | DK | | 3-1 | 22-12-31 | D00055A | H10 | | | D41695J | 13 | | | 001-099 |
| 3003B | 22 | GC | DK | | 3-0 | 22-12-31 | D00055A | H10 | | | D41695J | 13 | | | 115-199 |
| 3003R | 22 | GC | DK | | 0-0 | 22-12-31 | D00055A | J09 | | | D41695J | 4 | | | ALL |
| 3003Y | 22 | GC | DK | | 0-0 | 22-12-31 | D00055A | H09 | | | D41695J | 15 | | | ALL |
| 3004B | 22 | GC | DS | | 3-0 | 22-12-31 | D00055B | H10 | | | D41695J | 16 | | | ALL |
| 3004R | 22 | GC | DS | | 0-0 | 22-12-31 | D00055B | J09 | | | D41695J | 2 | | | ALL |
| 3004Y | 22 | GC | DS | | 0-0 | 22-12-31 | D00055B | H09 | | | D41695J | 18 | | | ALL |
| 3005B | 22 | GC | DU | | 3-0 | 22-12-31 | D00055B | D05 | | | D41695J | 37 | | | ALL |
| 3005R | 22 | GC | DU | | 0-0 | 22-12-31 | D00055B | C05 | | | D41695J | 36 | | | ALL |
| 3005Y | 22 | GC | DU | | 0-0 | 22-12-31 | D00055B | D06 | | | D41695J | 38 | | | ALL |
| 3006B | 22 | GC | ED | | 2-10 | 22-13-31 | D00055B | K06 | | | D41622J | 8 | | | 001-099 |
| 3006B | 22 | GC | ED | | 4-0 | 22-13-31 | D00055B | K06 | | | D41622J | 8 | | | 115-199 |
| 3006R | 22 | GC | ED | | 0-0 | 22-13-31 | D00055B | J05 | | | D41622J | 7 | | | ALL |
| 3006Y | 22 | GC | ED | | 0-0 | 22-13-31 | D00055B | K05 | | | D41622J | 9 | | | ALL |
| 3007B | 22 | GC | EF | | 2-11 | 22-13-31 | D00055A | K06 | | | D41622J | 11 | | | 001-099 |
| 3007B | 22 | GC | EF | | 4-0 | 22-13-31 | D00055A | K06 | | | D41622J | 11 | | | 115-199 |
| 3007R | 22 | GC | EF | | 0-0 | 22-13-31 | D00055A | J05 | | | D41622J | 10 | | | ALL |
| 3007Y | 22 | GC | EF | | 0-0 | 22-13-31 | D00055A | K05 | | | D41622J | 12 | | | ALL |
| 3008B | 22 | GC | EH | | 3-0 | 22-13-31 | D00055B | J06 | | | D41695J | 22 | | | ALL |
| 3008R | 22 | GC | EH | | 0-0 | 22-13-31 | D00055B | H06 | | | D41695J | 23 | | | ALL |
| 3008Y | 22 | GC | EH | | 0-0 | 22-13-31 | D00055B | H05 | | | D41695J | 24 | | | ALL |
| 3009B | 22 | GC | EI | | 3-1 | 22-13-31 | D00055A | J06 | | | D41695J | 3 | | | 001-099 |
| 3009B | 22 | GC | EI | | 3-0 | 22-13-31 | D00055A | J06 | | | D41695J | 3 | | | 115-199 |
| 3009R | 22 | GC | EI | | 0-0 | 22-13-31 | D00055A | H06 | | | D41695J | 20 | | | ALL |
| 3009Y | 22 | GC | EI | | 0-0 | 22-13-31 | D00055A | H05 | | | D41695J | 21 | | | ALL |
| 3011B | 24 | GM | GC | | 3-6 | 34-24-11 | D00447C | 10 | | | D42049J | 2 | | | 001-099 |
| 3011B | 24 | GM | GC | | 4-0 | 34-24-11 | D42049J | 2 | | | D00447C | 10 | | | 115-199 |
| 3011R | 24 | GM | GC | | 0-0 | 34-24-11 | D00447C | 9 | | | D42049J | 1 | | | 001-099 |
| 3011R | 24 | GM | GC | | 0-0 | 34-24-11 | D42049J | 1 | | | D00447C | 9 | | | 115-199 |
| 3011Y | 24 | GM | GC | | 0-0 | 34-24-11 | D00447C | 11 | | | D42049J | 3 | | | 001-099 |
| 3011Y | 24 | GM | GC | | 0-0 | 34-24-11 | D42049J | 3 | | | D00447C | 11 | | | 115-199 |
| 3501B | 24 | G3 | GQ | | 2-3 | 22-32-12 | D00383B | D15 | | | TB0205X | B119 | BJ | | 001-099 |
| 3501B | 24 | G3 | GQ | | 4-0 | 22-32-12 | D00383B | D15 | | | TB0205X | B119 | BJ | | 115-199 |
| 3501R | 24 | G3 | GQ | | 0-0 | 22-32-12 | D00383B | E09 | | | TB0205X | B120 | BJ | | ALL |
| 3501Y | 24 | G3 | GQ | | 0-0 | 22-32-12 | D00383B | G12 | | | TB0205X | C119 | BJ | | ALL |
| 3501Z | | | GQ | | 0-0 | 22-32-12 | D00383B | DED | | | GD02115 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 134

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5001B | 24 | G2 | BD | | 2-3 | 34-22-29 | D41567J | 8 | | | TB0205Y | C107 | BJ | | 001-099 |
| 5001B | 24 | G2 | BD | | 3-0 | 34-22-29 | TB0205Y | C107 | BJ | | D41567J | 8 | | | 115-199 |
| 5001R | 24 | G2 | BD | | 0-0 | 34-22-29 | D41567J | 7 | | | TB0205Y | C108 | BJ | | 001-099 |
| 5001R | 24 | G2 | BD | | 0-0 | 34-22-29 | TB0205Y | C108 | BJ | | D41567J | 7 | | | 115-199 |
| 5001Z | | | BD | | 0-0 | 34-22-29 | D41567J | 9 | | | GD02113 | ST.. | 2 | | 001-099 |
| 5001Z | | | BD | | 0-0 | 34-22-29 | GD02113 | ST.. | 2 | | D41567J | 9 | | | 115-199 |
| 5002B | 24 | G2 | BE | | 3-9 | 34-22-34 | D00085D | F05 | | | D41605J | 8 | | | 001-099 |
| 5002B | 24 | G2 | BE | | 3-0 | 34-22-34 | D41605J | 8 | | | D00085D | F05 | | | 115-199 |
| 5002R | 24 | G2 | BE | | 0-0 | 34-22-34 | D00085D | E05 | | | D41605J | 7 | | | 001-099 |
| 5002R | 24 | G2 | BE | | 0-0 | 34-22-34 | D41605J | 7 | | | D00085D | E05 | | | 115-199 |
| 5002Z | | | BE | | 0-0 | 34-22-34 | D00085D | DED | | | D41605J | | | BE | 001-099 |
| 5002Z | | | BE | | 0-0 | 34-22-34 | D41605J | | | BE | D00085D | DED | | | 115-199 |
| 5003B | 24 | G2 | BX | | 3-1 | 34-22-35 | D00085A | F05 | | | D41567J | 26 | | | 001-099 |
| 5003B | 24 | G2 | BX | | 3-0 | 34-22-35 | D41567J | 26 | | | D00085A | F05 | | | 115-199 |
| 5003R | 24 | G2 | BX | | 0-0 | 34-22-35 | D00085A | E05 | | | D41567J | 25 | | | 001-099 |
| 5003R | 24 | G2 | BX | | 0-0 | 34-22-35 | D41567J | 25 | | | D00085A | E05 | | | 115-199 |
| 5003Z | | | BX | | 0-0 | 34-22-35 | D00085A | DED | | | D41567J | | | BX | 001-099 |
| 5003Z | | | BX | | 0-0 | 34-22-35 | D41567J | | | BX | D00085A | DED | | | 115-199 |
| 5004B | 24 | G2 | CQ | | 3-11 | 34-22-38 | D00085D | B05 | | | D41349J | 35 | | | 001-099 |
| 5004B | 24 | G2 | CQ | | 4-0 | 34-22-38 | D00085D | B05 | | | D41349J | 35 | | | 115-199 |
| 5004R | 24 | G2 | CQ | | 0-0 | 34-22-38 | D00085D | A05 | | | D41349J | 34 | | | ALL |
| 5004Z | | | CQ | | 0-0 | 34-22-38 | D00085D | DED | | | D41349J | | | CQ | ALL |
| 5005B | 24 | G2 | CR | | 3-1 | 34-22-38 | D00085A | B05 | | | D41567J | 29 | | | 001-099 |
| 5005B | 24 | G2 | CR | | 3-0 | 34-22-38 | D00085A | B05 | | | D41567J | 29 | | | 115-199 |
| 5005R | 24 | G2 | CR | | 0-0 | 34-22-38 | D00085A | A05 | | | D41567J | 28 | | | ALL |
| 5005Z | | | CR | | 0-0 | 34-22-38 | D00085A | DED | | | D41567J | | | CR | ALL |
| 5006B | 24 | G2 | CS | | 3-0 | 34-22-38 | D00085B | B05 | | | TB0205Z | 55 | BJ | | ALL |
| 5006R | 24 | G2 | CS | | 0-0 | 34-22-38 | D00085B | A05 | | | TB0205Z | 56 | BJ | | ALL |
| 5006Z | | | CS | | 0-0 | 34-22-38 | D00085B | DED | | | GD02108 | ST.. | 2 | | ALL |
| 5007B | 24 | G2 | CT | | 3-9 | 34-22-38 | D00085D | B03 | | | D41605J | 25 | | | 001-099 |
| 5007B | 24 | G2 | CT | | 3-0 | 34-22-38 | D00085D | B03 | | | D41815J | 46 | | | 115-199 |
| 5007R | 24 | G2 | CT | | 0-0 | 34-22-38 | D00085D | A03 | | | D41605J | 24 | | | 001-099 |
| 5007R | 24 | G2 | CT | | 0-0 | 34-22-38 | D00085D | A03 | | | D41815J | 45 | | | 115-199 |
| 5007Z | | | CT | | 0-0 | 34-22-38 | D00085D | DED | | | D41605J | | | CT | 001-099 |
| 5007Z | | | CT | | 0-0 | 34-22-38 | D00085D | DED | | | D41815J | | | CT | 115-199 |
| 5008B | 24 | G2 | CU | | 3-1 | 34-22-38 | D00085A | B03 | | | D41567J | 14 | | | 001-099 |
| 5008R | 24 | G2 | CU | | 0-0 | 34-22-38 | D00085A | A03 | | | D41567J | 13 | | | 001-099 |
| 5008Z | | | CU | | 0-0 | 34-22-38 | D00085A | DED | | | D41567J | | | CU | 001-099 |
| 5009B | 24 | G2 | CV | | 3-2 | 34-22-39 | D00085B | H04 | | | D41395J | 5 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 135

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5009B | 24 | | G2 | CV | 3-0 | 34-22-39 | D41395J | 5 | | | D00085B | H04 | | | 115-199 |
| 5009R | 24 | | G2 | CV | 0-0 | 34-22-39 | D00085B | G04 | | | D41395J | 4 | | | 001-099 |
| 5009R | 24 | | G2 | CV | 0-0 | 34-22-39 | D41395J | 4 | | | D00085B | G04 | | | 115-199 |
| 5009Z | | | | CV | 0-0 | 34-22-39 | D00085B | DED | | | D41395J | | | CV | 001-099 |
| 5009Z | | | | CV | 0-0 | 34-22-39 | D41395J | | | CV | D00085B | DED | | | 115-199 |
| 5010B | 24 | | G2 | CW | 3-9 | 34-22-39 | D00085D | H02 | | | D41605J | 29 | | | 001-099 |
| 5010B | 24 | | G2 | CW | 3-0 | 34-22-39 | D41605J | 29 | | | D00085D | H02 | | | 115-199 |
| 5010R | 24 | | G2 | CW | 0-0 | 34-22-39 | D00085D | G02 | | | D41605J | 28 | | | 001-099 |
| 5010R | 24 | | G2 | CW | 0-0 | 34-22-39 | D41605J | 28 | | | D00085D | G02 | | | 115-199 |
| 5010Z | | | | CW | 0-0 | 34-22-39 | D00085D | DED | | | D41605J | | | CW | 001-099 |
| 5010Z | | | | CW | 0-0 | 34-22-39 | D41605J | | | CW | D00085D | DED | | | 115-199 |
| 5011B | 24 | | G2 | CX | 3-9 | 34-22-39 | D00085D | K03 | | | D41605J | 32 | | | 001-099 |
| 5011B | 24 | | G2 | CX | 3-0 | 34-22-39 | D41605J | 32 | | | D00085D | K03 | | | 115-199 |
| 5011R | 24 | | G2 | CX | 0-0 | 34-22-39 | D00085D | J03 | | | D41605J | 31 | | | 001-099 |
| 5011R | 24 | | G2 | CX | 0-0 | 34-22-39 | D41605J | 31 | | | D00085D | J03 | | | 115-199 |
| 5011Z | | | | CX | 0-0 | 34-22-39 | D00085D | DED | | | D41605J | | | CX | 001-099 |
| 5011Z | | | | CX | 0-0 | 34-22-39 | D41605J | | | CX | D00085D | DED | | | 115-199 |
| 5012B | 24 | | G2 | CY | 3-9 | 34-22-39 | D00085D | K01 | | | D41605J | 35 | | | 001-099 |
| 5012B | 24 | | G2 | CY | 3-0 | 34-22-39 | D41605J | 35 | | | D00085D | K01 | | | 115-199 |
| 5012R | 24 | | G2 | CY | 0-0 | 34-22-39 | D00085D | J01 | | | D41605J | 34 | | | 001-099 |
| 5012R | 24 | | G2 | CY | 0-0 | 34-22-39 | D41605J | 34 | | | D00085D | J01 | | | 115-199 |
| 5012Z | | | | CY | 0-0 | 34-22-39 | D00085D | DED | | | D41605J | | | CY | 001-099 |
| 5012Z | | | | CY | 0-0 | 34-22-39 | D41605J | | | CY | D00085D | DED | | | 115-199 |
| 5013B | 24 | | G2 | CZ | 2-9 | 34-22-39 | D00085A | D04 | | | TB0205Y | C101 | BJ | | 001-099 |
| 5013B | 24 | | G2 | CZ | 2-0 | 34-22-39 | D00085A | D04 | | | TB0205Y | C101 | BJ | | 115-199 |
| 5013R | 24 | | G2 | CZ | 0-0 | 34-22-39 | D00085A | C04 | | | TB0205Y | C102 | BJ | | ALL |
| 5013Z | | | | CZ | 0-0 | 34-22-39 | D00085A | DED | | | GD02114 | ST.. | 2 | | ALL |
| 5014B | 24 | | G2 | DA | 2-9 | 34-22-39 | D00085A | K05 | | | TB0205Z | 109 | BJ | | 001-099 |
| 5014B | 24 | | G2 | DA | 3-0 | 34-22-39 | D00085A | K05 | | | TB0205Z | 109 | BJ | | 115-199 |
| 5014R | 24 | | G2 | DA | 0-0 | 34-22-39 | D00085A | J05 | | | TB0205Z | 110 | BJ | | ALL |
| 5014Z | | | | DA | 0-0 | 34-22-39 | D00085A | DED | | | GD02114 | ST.. | 2 | | ALL |
| 5015B | 24 | | G2 | DB | 3-1 | 34-22-39 | D00085A | K01 | | | D41567J | 17 | | | 001-099 |
| 5015B | 24 | | G2 | DB | 3-0 | 34-22-39 | D41567J | 17 | | | D00085A | K01 | | | 115-199 |
| 5015R | 24 | | G2 | DB | 0-0 | 34-22-39 | D00085A | J01 | | | D41567J | 16 | | | 001-099 |
| 5015R | 24 | | G2 | DB | 0-0 | 34-22-39 | D41567J | 16 | | | D00085A | J01 | | | 115-199 |
| 5015Z | | | | DB | 0-0 | 34-22-39 | D00085A | DED | | | D41567J | | | DB | 001-099 |
| 5015Z | | | | DB | 0-0 | 34-22-39 | D41567J | | | DB | D00085A | DED | | | 115-199 |
| 5016B | 24 | | G2 | DC | 3-1 | 34-22-39 | D00085A | K03 | | | D41567J | 20 | | | 001-099 |
| 5016B | 24 | | G2 | DC | 3-0 | 34-22-39 | D41567J | 20 | | | D00085A | K03 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 136

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5016R | 24 | G2 | DC | | 0-0 | 34-22-39 | D00085A | J03 | | | D41567J | 19 | | | 001-099 |
| 5016R | 24 | G2 | DC | | 0-0 | 34-22-39 | D41567J | 19 | | | D00085A | J03 | | | 115-199 |
| 5016Z | | | DC | | 0-0 | 34-22-39 | D00085A | DED | | | D41567J | | DC | | 001-099 |
| 5016Z | | | DC | | 0-0 | 34-22-39 | D41567J | | | DC | D00085A | DED | | | 115-199 |
| 5017B | 24 | G2 | DD | | 3-1 | 34-22-39 | D00085A | H02 | | | D41567J | 23 | | | 001-099 |
| 5017B | 24 | G2 | DD | | 3-0 | 34-22-39 | D41567J | 23 | | | D00085A | H02 | | | 115-199 |
| 5017R | 24 | G2 | DD | | 0-0 | 34-22-39 | D00085A | G02 | | | D41567J | 22 | | | 001-099 |
| 5017R | 24 | G2 | DD | | 0-0 | 34-22-39 | D41567J | 22 | | | D00085A | G02 | | | 115-199 |
| 5017Z | | | DD | | 0-0 | 34-22-39 | D00085A | DED | | | D41567J | | DD | | 001-099 |
| 5017Z | | | DD | | 0-0 | 34-22-39 | D41567J | | | DD | D00085A | DED | | | 115-199 |
| 5018B | 24 | 7K | DG | | 2-9 | 34-43-11 | D41567J | 10 | | | TB0206A | C001 | 2 | | 001, 003-099 |
| 5018B | 24 | 7K | DG | | 6-0 | 34-43-15 | D23005J | 7 | | | TB0206A | C001 | 2 | | 002 |
| 5018B | 24 | 7K | DG | | 3-0 | 34-43-11 | TB0206A | C001 | 2 | | D41567J | 10 | | | 115-199 |
| 5018W | 24 | 7K | DG | | 0-0 | 34-43-11 | D41567J | 11 | | | TB0206A | A001 | 2 | | 001, 003-099 |
| 5018W | 24 | 7K | DG | | 0-0 | 34-43-15 | D23005J | 6 | | | TB0206A | A001 | 2 | | 002 |
| 5018W | 24 | 7K | DG | | 0-0 | 34-43-11 | TB0206A | A001 | 2 | | D41567J | 11 | | | 115-199 |
| 5018Z | | | DG | | 0-0 | 34-43-11 | D41567J | 12 | | | GD02117 | ST.. | 2 | | 001, 003-099 |
| 5018Z | | | DG | | 0-0 | 34-43-15 | D23005J | 8 | | | GD02117 | ST.. | 2 | | 002 |
| 5018Z | | | DG | | 0-0 | 34-43-11 | GD02117 | ST.. | 2 | | D41567J | 12 | | | 115-199 |
| 5019B | 24 | 7K | DE | | 0-6 | 34-43-11 | D00085A | F01 | | | TB0206A | C001 | 2 | | 001, 003-099, 115-199 |
| 5019B | 24 | 7K | DE | | 0-6 | 34-43-15 | D00085A | F01 | | | TB0206A | C001 | 2 | | 002 |
| 5019W | 24 | 7K | DE | | 0-0 | 34-43-11 | D00085A | E01 | | | TB0206A | A001 | 2 | | 001, 003-099, 115-199 |
| 5019W | 24 | 7K | DE | | 0-0 | 34-43-15 | D00085A | E01 | | | TB0206A | A001 | 2 | | 002 |
| 5019Z | | | DE | | 0-0 | 34-43-11 | D00085A | DED | | | GD02117 | ST.. | 2 | | 001, 003-099, 115-199 |
| 5019Z | | | DE | | 0-0 | 34-43-15 | D00085A | DED | | | GD02117 | ST.. | 2 | | 002 |
| 5020B | 24 | 7K | DF | | 0-6 | 34-43-11 | D00085A | F03 | | | TB0206A | C002 | 2 | | 001, 003-099, 115-199 |
| 5020B | 24 | 7K | DF | | 0-6 | 34-43-15 | D00085A | F03 | | | TB0206A | C002 | 2 | | 002 |
| 5020W | 24 | 7K | DF | | 0-0 | 34-43-11 | D00085A | E03 | | | TB0206A | A002 | 2 | | 001, 003-099, 115-199 |
| 5020W | 24 | 7K | DF | | 0-0 | 34-43-15 | D00085A | E03 | | | TB0206A | A002 | 2 | | 002 |
| 5020Z | | | DF | | 0-0 | 34-43-11 | D00085A | DED | | | GD02117 | ST.. | 2 | | 001, 003-099, 115-199 |
| 5020Z | | | DF | | 0-0 | 34-43-15 | D00085A | DED | | | GD02117 | ST.. | 2 | | 002 |
| 5021B | 24 | 7K | DH | | 3-5 | 34-43-11 | D41605J | 11 | | | TB0206A | C002 | 2 | | 001, 003-099 |
| 5021B | 24 | 7K | DH | | 6-0 | 34-43-15 | D23003J | 6 | | | TB0206A | C002 | 2 | | 002 |
| 5021B | 24 | 7K | DH | | 4-0 | 34-43-11 | TB0206A | C002 | 2 | | D41605J | 11 | | | 115-199 |
| 5021W | 24 | 7K | DH | | 0-0 | 34-43-11 | D41605J | 10 | | | TB0206A | A002 | 2 | | 001, 003-099 |
| 5021W | 24 | 7K | DH | | 0-0 | 34-43-15 | D23003J | 5 | | | TB0206A | A002 | 2 | | 002 |
| 5021W | 24 | 7K | DH | | 0-0 | 34-43-11 | TB0206A | A002 | 2 | | D41605J | 10 | | | 115-199 |
| 5021Z | | | DH | | 0-0 | 34-43-11 | D41605J | 12 | | | GD02117 | ST.. | 2 | | 001, 003-099 |
| 5021Z | | | DH | | 0-0 | 34-43-15 | D23003J | 4 | | | GD02117 | ST.. | 2 | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 137

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-------------------------------------|---------|----------|---------|------|--------|-------|------|---------|--------|-------------|---------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5021Z | | | | DH | 0-0 | 34-43-11 | GD02117 | ST.. | 2 | | | D41605J | 12 | | 115-199 |
| 5022B | 24 | G2 | | DI | 3-11 | 34-43-11 | D41605J | 15 | | | | TB0205Y | A111 | BJ | 001-099 |
| 5022B | 24 | G2 | | DI | 5-0 | 34-43-11 | TB0205Y | A111 | BJ | | | D41605J | 15 | | 115-199 |
| 5022R | 24 | G2 | | DI | 0-0 | 34-43-11 | D41605J | 14 | | | | TB0205Y | A112 | BJ | 001-099 |
| 5022R | 24 | G2 | | DI | 0-0 | 34-43-11 | TB0205Y | A112 | BJ | | | D41605J | 14 | | 115-199 |
| 5022Z | | | | DI | 0-0 | 34-43-11 | D41605J | 13 | | | | GD02115 | ST.. | 2 | 001-099 |
| 5022Z | | | | DI | 0-0 | 34-43-11 | GD02115 | ST.. | 2 | | | D41605J | 13 | | 115-199 |
| 5023B | 24 | G2 | | BC | 2-3 | 34-22-19 | D41567J | 5 | | | | TB0205Z | 109 | BJ | 001-099 |
| 5023B | 24 | G2 | | BC | 3-0 | 34-22-19 | D41567J | 5 | | | | TB0205Z | 109 | BJ | 115-199 |
| 5023R | 24 | G2 | | BC | 0-0 | 34-22-19 | D41567J | 4 | | | | TB0205Z | 110 | BJ | ALL |
| 5023Z | | | | BC | 0-0 | 34-22-19 | D41567J | 6 | | | | GD02114 | ST.. | 2 | ALL |
| 5024B | 24 | G2 | | GN | 2-4 | 34-31-31 | D00207B | C13 | | | | D42109J | 13 | | 001-099 |
| 5024B | 24 | G2 | | GN | 2-0 | 34-31-31 | D42109J | 13 | | | | D02943B | K01 | | 115-199 |
| 5024R | 24 | G2 | | GN | 0-0 | 34-31-31 | D00207B | B13 | | | | D42109J | 14 | | 001-099 |
| 5024R | 24 | G2 | | GN | 0-0 | 34-31-31 | D42109J | 14 | | | | D02943B | J01 | | 115-199 |
| 5024Z | | | | GN | 0-0 | 34-31-31 | D00207B | DED | | | | D42109J | | GN | 001-099 |
| 5024Z | | | | GN | 0-0 | 34-31-31 | D42109J | | | GN | | D02943B | DED | | 115-199 |
| 5025B | 24 | G2 | | AA | 2-3 | 31-31-41 | TB0205Y | A067 | BJ | | | D41395J | 8 | | 001-099 |
| 5025B | 24 | G2 | | AA | 3-0 | 31-31-21 | D41395J | 8 | | | | TB0205Y | A067 | BJ | 115-199 |
| 5025R | 24 | G2 | | AA | 0-0 | 31-31-41 | TB0205Y | A068 | BJ | | | D41395J | 9 | | 001-099 |
| 5025R | 24 | G2 | | AA | 0-0 | 31-31-21 | D41395J | 9 | | | | TB0205Y | A068 | BJ | 115-199 |
| 5025Z | | | | AA | 0-0 | 31-31-41 | GD02109 | ST.. | 2 | | | D41395J | 7 | | 001-099 |
| 5025Z | | | | AA | 0-0 | 31-31-21 | D41395J | 7 | | | | GD02109 | ST.. | 2 | 115-199 |
| 5026B | 24 | G2 | | LG | 3-5 | 31-31-42 | D41815J | 20 | | | | TB0205Z | 121 | BJ | 001-099 |
| 5026B | 24 | G2 | | AB | 4-0 | 31-31-22 | D41815J | 20 | | | | TB0205Z | 121 | BJ | 115-199 |
| 5026R | 24 | G2 | | LG | 0-0 | 31-31-42 | D41815J | 19 | | | | TB0205Z | 122 | BJ | 001-099 |
| 5026R | 24 | G2 | | AB | 0-0 | 31-31-22 | D41815J | 19 | | | | TB0205Z | 122 | BJ | 115-199 |
| 5026Z | | | | LG | 0-0 | 31-31-42 | D41815J | 21 | | | | GD02115 | ST.. | 2 | 001-099 |
| 5026Z | | | | AB | 0-0 | 31-31-22 | D41815J | 21 | | | | GD02115 | ST.. | 2 | 115-199 |
| 5027B | 24 | G2 | | EP | 3-0 | 22-41-12 | D00055A | A02 | | | | D41097J | 27 | | ALL |
| 5027R | 24 | G2 | | EP | 0-0 | 22-41-12 | D00055A | A01 | | | | D41097J | 26 | | ALL |
| 5027Z | | | | EP | 0-0 | 22-41-12 | D00055A | DED | | | | D41097J | | EP | ALL |
| 5028B | 24 | G2 | | EQ | 4-4 | 22-41-12 | D00383A | F01 | | | | D41097J | 30 | | 001-099 |
| 5028B | 24 | G2 | | EQ | 4-0 | 22-41-12 | D00383A | F01 | | | | D41097J | 30 | | 115-199 |
| 5028R | 24 | G2 | | EQ | 0-0 | 22-41-12 | D00383A | F02 | | | | D41097J | 29 | | ALL |
| 5028Z | | | | EQ | 0-0 | 22-41-12 | D00383A | DED | | | | D41097J | | EQ | ALL |
| 5029B | 24 | G2 | | ER | 2-4 | 22-41-11 | D00055B | C04 | | | | D41815J | 8 | | 001-099 |
| 5029B | 24 | G2 | | ER | 2-0 | 22-41-11 | D00055B | C04 | | | | D41815J | 8 | | 115-199 |
| 5029R | 24 | G2 | | ER | 0-0 | 22-41-11 | D00055B | C03 | | | | D41815J | 7 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 138

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5029Z | | | | ER | 0-0 | 22-41-11 | D00055B | DED | | | D41815J | | | ER | ALL |
| 5030B | 24 | G2 | | ES | 3-11 | 22-41-11 | D41097J | 24 | | | TB0205Z | 121 | BJ | | 001-099 |
| 5030B | 24 | G2 | | ES | 5-0 | 22-41-11 | TB0205Z | 121 | BJ | | D41097J | 24 | | | 115-199 |
| 5030R | 24 | G2 | | ES | 0-0 | 22-41-11 | D41097J | 23 | | | TB0205Z | 122 | BJ | | 001-099 |
| 5030R | 24 | G2 | | ES | 0-0 | 22-41-11 | TB0205Z | 122 | BJ | | D41097J | 23 | | | 115-199 |
| 5030Z | | | | ES | 0-0 | 22-41-11 | D41097J | 25 | | | GD02115 | ST.. | 2 | | 001-099 |
| 5030Z | | | | ES | 0-0 | 22-41-11 | GD02115 | ST.. | 2 | | D41097J | 25 | | | 115-199 |
| 5031B | 24 | G2 | | AY | 2-3 | 22-32-12 | D00383B | G06 | | | TB0205Z | 121 | BJ | | 001-099 |
| 5031B | 24 | G2 | | AY | 3-0 | 22-32-12 | TB0205Z | 121 | BJ | | D00383B | G06 | | | 115-199 |
| 5031R | 24 | G2 | | AY | 0-0 | 22-32-12 | D00383B | H06 | | | TB0205Z | 122 | BJ | | 001-099 |
| 5031R | 24 | G2 | | AY | 0-0 | 22-32-12 | TB0205Z | 122 | BJ | | D00383B | H06 | | | 115-199 |
| 5031Z | | | | AY | 0-0 | 22-32-12 | D00383B | DED | | | GD02115 | ST.. | 2 | | 001-099 |
| 5031Z | | | | AY | 0-0 | 22-32-12 | GD02115 | ST.. | 2 | | D00383B | DED | | | 115-199 |
| 5032B | 24 | G2 | | BA | 2-3 | 22-32-12 | D00383B | J14 | | | TB0205Y | C107 | BJ | | 001-099 |
| 5032B | 24 | G2 | | BA | 3-0 | 22-32-12 | D00383B | J14 | | | TB0205Y | C107 | BJ | | 115-199 |
| 5032R | 24 | G2 | | BA | 0-0 | 22-32-12 | D00383B | J15 | | | TB0205Y | C108 | BJ | | ALL |
| 5032Z | | | | BA | 0-0 | 22-32-12 | D00383B | DED | | | GD02114 | ST.. | 2 | | ALL |
| 5033B | 24 | G2 | | BB | 2-3 | 22-32-12 | D00383B | J13 | | | TB0205Z | 109 | BJ | | 001-099 |
| 5033B | 24 | G2 | | BB | 3-0 | 22-32-12 | D00383B | J13 | | | TB0205Z | 109 | BJ | | 115-199 |
| 5033R | 24 | G2 | | BB | 0-0 | 22-32-12 | D00383B | J12 | | | TB0205Z | 110 | BJ | | ALL |
| 5033Z | | | | BB | 0-0 | 22-32-12 | D00383B | DED | | | GD02114 | ST.. | 2 | | ALL |
| 5034B | 24 | G2 | | AX | 3-11 | 22-32-12 | D41097J | 5 | | | TB0205Z | 121 | BJ | | 001-099 |
| 5034B | 24 | G2 | | AX | 5-0 | 22-32-12 | D41097J | 5 | | | TB0205Z | 121 | BJ | | 115-199 |
| 5034R | 24 | G2 | | AX | 0-0 | 22-32-12 | D41097J | 4 | | | TB0205Z | 122 | BJ | | ALL |
| 5034Z | | | | AX | 0-0 | 22-32-12 | D41097J | 6 | | | GD02115 | ST.. | 2 | | ALL |
| 5035B | 24 | G2 | | AZ | 4-1 | 22-32-12 | D41349J | 2 | | | TB0205Z | 121 | BJ | | 001-099 |
| 5035B | 24 | G2 | | AZ | 5-0 | 22-32-12 | D41349J | 2 | | | TB0205Z | 121 | BJ | | 115-199 |
| 5035R | 24 | G2 | | AZ | 0-0 | 22-32-12 | D41349J | 1 | | | TB0205Z | 122 | BJ | | ALL |
| 5035Z | | | | AZ | 0-0 | 22-32-12 | D41349J | 3 | | | GD02115 | ST.. | 2 | | ALL |
| 5036B | 24 | G2 | | AN | 2-3 | 22-32-11 | D00383B | J08 | | | TB0205Y | C111 | BJ | | 001-099 |
| 5036B | 24 | G2 | | AN | 3-0 | 22-32-11 | D00383B | J08 | | | TB0205Y | C111 | BJ | | 115-199 |
| 5036R | 24 | G2 | | AN | 0-0 | 22-32-11 | D00383B | K08 | | | TB0205Y | C112 | BJ | | ALL |
| 5036Z | | | | AN | 0-0 | 22-32-11 | D00383B | DED | | | GD02114 | ST.. | 2 | | ALL |
| 5037B | 24 | G2 | | AO | 2-8 | 22-32-11 | D00383A | C03 | | | D42063J | 2 | | | 001-099 |
| 5037B | 24 | G2 | | AO | 3-0 | 22-32-11 | D42063J | 2 | | | D00383A | C03 | | | 115-199 |
| 5037R | 24 | G2 | | AO | 0-0 | 22-32-11 | D00383A | C02 | | | D42063J | 1 | | | 001-099 |
| 5037R | 24 | G2 | | AO | 0-0 | 22-32-11 | D42063J | 1 | | | D00383A | C02 | | | 115-199 |
| 5037Z | | | | AO | 0-0 | 22-32-11 | D00383A | DED | | | D42063J | | | AO | 001-099 |
| 5037Z | | | | AO | 0-0 | 22-32-11 | D42063J | | | AO | D00383A | DED | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 139

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | To | | | | | | | | | | |
|------------|-------------|----|-------|-------------------------------------|------|----------|---------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 5038B | 24 | G2 | AP | | 2-6 | 22-32-11 | D00383A | A06 | | | | D41819J | 3 | | | 001-099 |
| 5038B | 24 | G2 | AP | | 3-0 | 22-32-11 | D41819J | 3 | | | | D00383A | A06 | | | 115-199 |
| 5038R | 24 | G2 | AP | | 0-0 | 22-32-11 | D00383A | A07 | | | | D41819J | 2 | | | 001-099 |
| 5038R | 24 | G2 | AP | | 0-0 | 22-32-11 | D41819J | 2 | | | | D00383A | A07 | | | 115-199 |
| 5038Z | | | AP | | 0-0 | 22-32-11 | D00383A | DED | | | | D41819J | | AP | | 001-099 |
| 5038Z | | | AP | | 0-0 | 22-32-11 | D41819J | | | | AP | D00383A | DED | | | 115-199 |
| 5039B | 24 | G2 | AQ | | 2-6 | 22-32-11 | D00383A | A09 | | | | D41819J | 6 | | | 001-099 |
| 5039B | 24 | G2 | AQ | | 3-0 | 22-32-11 | D41819J | 6 | | | | D00383A | A09 | | | 115-199 |
| 5039R | 24 | G2 | AQ | | 0-0 | 22-32-11 | D00383A | A08 | | | | D41819J | 5 | | | 001-099 |
| 5039R | 24 | G2 | AQ | | 0-0 | 22-32-11 | D41819J | 5 | | | | D00383A | A08 | | | 115-199 |
| 5039Z | | | AQ | | 0-0 | 22-32-11 | D00383A | DED | | | | D41819J | | AQ | | 001-099 |
| 5039Z | | | AQ | | 0-0 | 22-32-11 | D41819J | | | | AQ | D00383A | DED | | | 115-199 |
| 5040B | 24 | G2 | AR | | 2-0 | 22-32-11 | D41819J | 9 | | | | TB0205Y | A111 | BJ | | 001-099 |
| 5040B | 24 | G2 | AR | | 3-0 | 22-32-11 | D41819J | 9 | | | | TB0205Y | A111 | BJ | | 115-199 |
| 5040R | 24 | G2 | AR | | 0-0 | 22-32-11 | D41819J | 8 | | | | TB0205Y | A112 | BJ | | ALL |
| 5040Z | | | AR | | 0-0 | 22-32-11 | D41819J | 10 | | | | GD02114 | ST.. | 2 | | ALL |
| 5041B | 24 | G2 | AS | | 2-4 | 22-32-11 | D00383A | J01 | | | | TB0205Y | A111 | BJ | | 001-099 |
| 5041B | 24 | G2 | AS | | 3-0 | 22-32-11 | TB0205Y | A111 | BJ | | | D00383A | J01 | | | 115-199 |
| 5041R | 24 | G2 | AS | | 0-0 | 22-32-11 | D00383A | J02 | | | | TB0205Y | A112 | BJ | | 001-099 |
| 5041R | 24 | G2 | AS | | 0-0 | 22-32-11 | TB0205Y | A112 | BJ | | | D00383A | J02 | | | 115-199 |
| 5041Z | | | AS | | 0-0 | 22-32-11 | D00383A | DED | | | | GD02114 | ST.. | 2 | | 001-099 |
| 5041Z | | | AS | | 0-0 | 22-32-11 | GD02114 | ST.. | 2 | | | D00383A | DED | | | 115-199 |
| 5042B | 24 | G2 | AT | | 4-5 | 22-32-11 | D00383B | A15 | | | | D41349J | 11 | | | 001-099 |
| 5042B | 24 | G2 | AT | | 4-0 | 22-32-11 | D41349J | 11 | | | | D00383B | A15 | | | 115-199 |
| 5042R | 24 | G2 | AT | | 0-0 | 22-32-11 | D00383B | B15 | | | | D41349J | 10 | | | 001-099 |
| 5042R | 24 | G2 | AT | | 0-0 | 22-32-11 | D41349J | 10 | | | | D00383B | B15 | | | 115-199 |
| 5042Z | | | AT | | 0-0 | 22-32-11 | D00383B | DED | | | | D41349J | | AT | | 001-099 |
| 5042Z | | | AT | | 0-0 | 22-32-11 | D41349J | | | | AT | D00383B | DED | | | 115-199 |
| 5044B | 24 | G2 | AV | | 2-8 | 22-32-11 | D00383B | B14 | | | | D41823J | 2 | | | 001-099 |
| 5044B | 24 | G2 | AV | | 3-0 | 22-32-11 | D41823J | 2 | | | | D00383B | B14 | | | 115-199 |
| 5044R | 24 | G2 | AV | | 0-0 | 22-32-11 | D00383B | A14 | | | | D41823J | 1 | | | 001-099 |
| 5044R | 24 | G2 | AV | | 0-0 | 22-32-11 | D41823J | 1 | | | | D00383B | A14 | | | 115-199 |
| 5044Z | | | AV | | 0-0 | 22-32-11 | D00383B | DED | | | | D41823J | | AV | | 001-099 |
| 5044Z | | | AV | | 0-0 | 22-32-11 | D41823J | | | | AV | D00383B | DED | | | 115-199 |
| 5045B | 24 | G2 | AW | | 2-8 | 22-32-11 | D00383B | B13 | | | | D41823J | 5 | | | 001-099 |
| 5045B | 24 | G2 | AW | | 3-0 | 22-32-11 | D41823J | 5 | | | | D00383B | B13 | | | 115-199 |
| 5045R | 24 | G2 | AW | | 0-0 | 22-32-11 | D00383B | A13 | | | | D41823J | 4 | | | 001-099 |
| 5045R | 24 | G2 | AW | | 0-0 | 22-32-11 | D41823J | 4 | | | | D00383B | A13 | | | 115-199 |
| 5045Z | | | AW | | 0-0 | 22-32-11 | D00383B | DED | | | | D41823J | | AW | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 140

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5045Z | | | | AW | 0-0 | 22-32-11 | D41823J | | | AW | D00383B | DED | | | 115-199 |
| 5046B | 24 | G2 | DL | | 3-1 | 22-12-11 | D00085A | B01 | | | D41567J | 40 | | | 001-099 |
| 5046B | 24 | G2 | DL | | 3-0 | 22-12-11 | D00085A | B01 | | | D41567J | 40 | | | 115-199 |
| 5046R | 24 | G2 | DL | | 0-0 | 22-12-11 | D00085A | A01 | | | D41567J | 39 | | | ALL |
| 5046Z | | | DL | | 0-0 | 22-12-11 | D00085A | DED | | | D41567J | | | DL | ALL |
| 5047B | 24 | G2 | DN | | 2-9 | 22-12-31 | D42049J | 23 | | | TB0205Y | A075 | BJ | | 001-099 |
| 5047B | 24 | G2 | DN | | 5-0 | 22-12-31 | D42049J | 23 | | | TB0205Y | A075 | BJ | | 115-199 |
| 5047R | 24 | G2 | DN | | 0-0 | 22-12-31 | D42049J | 24 | | | TB0205Y | A076 | BJ | | ALL |
| 5047Z | | | DN | | 0-0 | 22-12-31 | D42049J | 25 | | | GD02110 | ST.. | 2 | | ALL |
| 5048B | 24 | G2 | DO | | 2-10 | 22-12-31 | D00055B | B04 | | | TB0205Y | A075 | BJ | | 001-099 |
| 5048B | 24 | G2 | DO | | 5-0 | 22-12-31 | D00055B | B04 | | | TB0205Y | A075 | BJ | | 115-199 |
| 5048R | 24 | G2 | DO | | 0-0 | 22-12-31 | D00055B | B03 | | | TB0205Y | A076 | BJ | | ALL |
| 5048Z | | | DO | | 0-0 | 22-12-31 | D00055B | DED | | | GD02110 | ST.. | 2 | | ALL |
| 5049B | 24 | G2 | DP | | 2-5 | 22-12-31 | D00055B | C02 | | | D41395J | 13 | | | 001-099 |
| 5049B | 24 | G2 | DP | | 2-0 | 22-12-31 | D41395J | 13 | | | D00055B | C02 | | | 115-199 |
| 5049R | 24 | G2 | DP | | 0-0 | 22-12-31 | D00055B | C01 | | | D41395J | 12 | | | 001-099 |
| 5049R | 24 | G2 | DP | | 0-0 | 22-12-31 | D41395J | 12 | | | D00055B | C01 | | | 115-199 |
| 5049Z | | | DP | | 0-0 | 22-12-31 | D00055B | DED | | | D41395J | | | DP | 001-099 |
| 5049Z | | | DP | | 0-0 | 22-12-31 | D41395J | | DP | | D00055B | DED | | | 115-199 |
| 5050B | 24 | G2 | DQ | | 3-8 | 22-12-31 | D00055A | D09 | | | D41643J | 8 | | | 001-099 |
| 5050B | 24 | G2 | DQ | | 4-0 | 22-12-31 | D00055A | D09 | | | D41643J | 8 | | | 115-199 |
| 5050R | 24 | G2 | DQ | | 0-0 | 22-12-31 | D00055A | C09 | | | D41643J | 7 | | | ALL |
| 5050Z | | | DQ | | 0-0 | 22-12-31 | D00055A | DED | | | D41643J | | | DQ | ALL |
| 5051B | 24 | G2 | DW | | 2-4 | 22-12-31 | D41395J | 23 | | | TB0205Y | A069 | BJ | | 001-099 |
| 5051B | 24 | G2 | DW | | 3-0 | 22-12-31 | D41395J | 23 | | | TB0205Y | A069 | BJ | | 115-199 |
| 5051R | 24 | G2 | DW | | 0-0 | 22-12-31 | D41395J | 22 | | | TB0205Y | A070 | BJ | | ALL |
| 5051Z | | | DW | | 0-0 | 22-12-31 | D41395J | 24 | | | GD02110 | ST.. | 2 | | ALL |
| 5052B | 24 | G2 | DV | | 2-5 | 22-12-31 | D00055B | B02 | | | TB0205Y | A069 | BJ | | 001-099 |
| 5052B | 24 | G2 | DV | | 3-0 | 22-12-31 | D00055B | B02 | | | TB0205Y | A069 | BJ | | 115-199 |
| 5052R | 24 | G2 | DV | | 0-0 | 22-12-31 | D00055B | B01 | | | TB0205Y | A070 | BJ | | ALL |
| 5052Z | | | DV | | 0-0 | 22-12-31 | D00055B | DED | | | GD02110 | ST.. | 2 | | ALL |
| 5053B | 24 | G2 | DX | | 3-0 | 22-12-31 | D00085B | B01 | | | TB0205Y | A069 | BJ | | 001-099 |
| 5053B | 24 | G2 | DX | | 4-0 | 22-12-31 | D00085B | B01 | | | TB0205Y | A069 | BJ | | 115-199 |
| 5053R | 24 | G2 | DX | | 0-0 | 22-12-31 | D00085B | A01 | | | TB0205Y | A070 | BJ | | ALL |
| 5053Z | | | DX | | 0-0 | 22-12-31 | D00085B | DED | | | GD02110 | ST.. | 2 | | ALL |
| 5054B | 24 | G2 | GB | | 2-3 | 22-13-11 | D41567J | 43 | | | TB0205Y | C111 | BJ | | 001-099 |
| 5054B | 24 | G2 | GB | | 3-0 | 22-13-11 | D41567J | 43 | | | TB0205Y | C111 | BJ | | 115-199 |
| 5054R | 24 | G2 | GB | | 0-0 | 22-13-11 | D41567J | 42 | | | TB0205Y | C112 | BJ | | ALL |
| 5054Z | | | GB | | 0-0 | 22-13-11 | D41567J | 44 | | | GD02114 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 141

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 5055B | 24 | G2 | EB | 2-3 | 22-13-31 | D00055B | E02 | | | | TB0205Z | 55 | BJ | | 001-099 | |
| 5055B | 24 | G2 | EB | 3-0 | 22-13-31 | D00055B | E02 | | | | TB0205Z | 55 | BJ | | 115-199 | |
| 5055R | 24 | G2 | EB | 0-0 | 22-13-31 | D00055B | E01 | | | | TB0205Z | 56 | BJ | | ALL | |
| 5055Z | | | EB | 0-0 | 22-13-31 | D00055B | DED | | | | GD02108 | ST.. | 2 | | ALL | |
| 5056B | 24 | G2 | DY | 3-8 | 22-13-31 | D00055A | B09 | | | | TB0205Y | C111 | BJ | | 001-099 | |
| 5056B | 24 | G2 | DY | 4-0 | 22-13-31 | TB0205Y | C111 | BJ | | | D00055A | B09 | | | 115-199 | |
| 5056R | 24 | G2 | DY | 0-0 | 22-13-31 | D00055A | A09 | | | | TB0205Y | C112 | BJ | | 001-099 | |
| 5056R | 24 | G2 | DY | 0-0 | 22-13-31 | TB0205Y | C112 | BJ | | | D00055A | A09 | | | 115-199 | |
| 5056Z | | | DY | 0-0 | 22-13-31 | D00055A | DED | | | | GD02114 | ST.. | 2 | | 001-099 | |
| 5056Z | | | DY | 0-0 | 22-13-31 | GD02114 | ST.. | 2 | | | D00055A | DED | | | 115-199 | |
| 5057B | 24 | G2 | EA | 2-5 | 22-13-31 | D00055B | A02 | | | | TB0205Y | C069 | BJ | | 001-099 | |
| 5057B | 24 | G2 | EA | 3-0 | 22-13-31 | TB0205Y | C069 | BJ | | | D00055B | A02 | | | 115-199 | |
| 5057R | 24 | G2 | EA | 0-0 | 22-13-31 | D00055B | A01 | | | | TB0205Y | C070 | BJ | | 001-099 | |
| 5057R | 24 | G2 | EA | 0-0 | 22-13-31 | TB0205Y | C070 | BJ | | | D00055B | A01 | | | 115-199 | |
| 5057Z | | | EA | 0-0 | 22-13-31 | D00055B | DED | | | | GD02109 | ST.. | 2 | | 001-099 | |
| 5057Z | | | EA | 0-0 | 22-13-31 | GD02109 | ST.. | 2 | | | D00055B | DED | | | 115-199 | |
| 5058B | 24 | G2 | DZ | 3-11 | 22-13-31 | D00207B | C07 | | | | TB0205Y | C069 | BJ | | 001-099 | |
| 5058B | 24 | G2 | DZ | 5-0 | 22-13-31 | D02943B | B01 | | | | TB0205Y | C069 | BJ | | 115-199 | |
| 5058R | 24 | G2 | DZ | 0-0 | 22-13-31 | D00207B | B07 | | | | TB0205Y | C070 | BJ | | 001-099 | |
| 5058R | 24 | G2 | DZ | 0-0 | 22-13-31 | D02943B | A01 | | | | TB0205Y | C070 | BJ | | 115-199 | |
| 5058Z | | | DZ | 0-0 | 22-13-31 | D00207B | DED | | | | GD02109 | ST.. | 2 | | 001-099 | |
| 5058Z | | | DZ | 0-0 | 22-13-31 | D02943B | DED | | | | GD02109 | ST.. | 2 | | 115-199 | |
| 5059B | 24 | G2 | EJ | 3-2 | 22-14-11 | D42021J | 13 | | | | TB0205Z | 109 | BJ | | 001-099 | |
| 5059B | 24 | G2 | EJ | 4-0 | 22-14-11 | D42021J | 13 | | | | TB0205Z | 109 | BJ | | 115-199 | |
| 5059R | 24 | G2 | EJ | 0-0 | 22-14-11 | D42021J | 12 | | | | TB0205Z | 110 | BJ | | ALL | |
| 5059Z | | | EJ | 0-0 | 22-14-11 | D42021J | 14 | | | | GD02114 | ST.. | 2 | | ALL | |
| 5060B | 24 | G2 | EK | 2-2 | 22-14-21 | D42083J | 10 | | | | TB0205Y | C107 | BJ | | 001-099 | |
| 5060B | 24 | G2 | EK | 3-0 | 22-14-21 | D42083J | 10 | | | | TB0205Y | C107 | BJ | | 115-199 | |
| 5060R | 24 | G2 | EK | 0-0 | 22-14-21 | D42083J | 9 | | | | TB0205Y | C108 | BJ | | ALL | |
| 5060Z | | | EK | 0-0 | 22-14-21 | D42083J | 11 | | | | GD02114 | ST.. | 2 | | ALL | |
| 5061B | 24 | G2 | EL | 2-5 | 22-15-11 | D00055B | F02 | | | | D41395J | 39 | | | 001-099 | |
| 5061B | 24 | G2 | EL | 2-0 | 22-15-11 | D00055B | F02 | | | | D41395J | 39 | | | 115-199 | |
| 5061R | 24 | G2 | EL | 0-0 | 22-15-11 | D00055B | F01 | | | | D41395J | 38 | | | ALL | |
| 5061Z | | | EL | 0-0 | 22-15-11 | D00055B | DED | | | | D41395J | | | EL | 001-099 | |
| 5061Z | | | EL | 0-0 | 22-15-11 | D41395J | | | | EL | D00055B | DED | | | 115-199 | |
| 5062B | 24 | G2 | EM | 3-2 | 22-15-11 | D00055A | E01 | | | | D41349J | 8 | | | 001-099 | |
| 5062B | 24 | G2 | EM | 3-0 | 22-15-11 | D00055A | E01 | | | | D41349J | 8 | | | 115-199 | |
| 5062R | 24 | G2 | EM | 0-0 | 22-15-11 | D00055A | D01 | | | | D41349J | 7 | | | ALL | |
| 5062Z | | | EM | 0-0 | 22-15-11 | D00055A | DED | | | | D41349J | | | EM | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 142

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5063B | 24 | G2 | EN | | 3-0 | 22-15-11 | D00055A | H03 | | | D41097J | 2 | | | ALL |
| 5063R | 24 | G2 | EN | | 0-0 | 22-15-11 | D00055A | G03 | | | D41097J | 1 | | | ALL |
| 5063Z | | | EN | | 0-0 | 22-15-11 | D00055A | DED | | | D41097J | | EN | | ALL |
| 5064B | 24 | G2 | EO | | 2-5 | 22-15-11 | D00055B | F03 | | | D41395J | 42 | | | 001-099 |
| 5064B | 24 | G2 | EO | | 2-0 | 22-15-11 | D00055B | F03 | | | D41395J | 42 | | | 115-199 |
| 5064R | 24 | G2 | EO | | 0-0 | 22-15-11 | D00055B | E03 | | | D41395J | 41 | | | ALL |
| 5064Z | | | EO | | 0-0 | 22-15-11 | D00055B | DED | | | D41395J | | EO | | ALL |
| 5065B | 24 | G2 | AC | | 2-8 | 34-46-12 | D00433B | D11 | | | D41433J | 5 | | | 001-099 |
| 5065B | 24 | G2 | AC | | 3-0 | 34-46-12 | D41433J | 5 | | | D00433B | CAP | Y | | 115-199 |
| 5065R | 24 | G2 | AC | | 0-0 | 34-46-12 | D00433B | C11 | | | D41433J | 4 | | | 001-099 |
| 5065R | 24 | G2 | AC | | 0-0 | 34-46-12 | D41433J | 4 | | | D00433B | CAP | Y | | 115-199 |
| 5065Z | | | AC | | 0-0 | 34-46-12 | D00433B | DED | | | D41433J | | | AC | 001-099 |
| 5065Z | | | AC | | 0-0 | 34-46-12 | D41433J | | | AC | D00433B | DED | | | 115-199 |
| 5066B | 24 | G2 | AD | | 2-7 | 34-46-12 | D00433B | D13 | | | D41349J | 18 | | | 001-008, 010-099 |
| 5066B | 24 | G2 | AD | | 2-11 | 34-46-12 | TB0205Y | A065 | BJ | | D41349J | 18 | | | 009 |
| 5066B | 24 | G2 | AD | | 4-0 | 34-46-12 | D41349J | 18 | | | TB0205Y | A065 | BJ | | 115-199 |
| 5066R | 24 | G2 | AD | | 0-0 | 34-46-12 | D00433B | C13 | | | D41349J | 17 | | | 001-008, 010-099 |
| 5066R | 24 | G2 | AD | | 0-0 | 34-46-12 | TB0205Y | A066 | BJ | | D41349J | 17 | | | 009 |
| 5066R | 24 | G2 | AD | | 0-0 | 34-46-12 | D41349J | 17 | | | TB0205Y | A066 | BJ | | 115-199 |
| 5066Z | | | AD | | 0-0 | 34-46-12 | D00433B | DED | | | D41349J | | | AD | 001-008, 010-099 |
| 5066Z | | | AD | | 0-0 | 34-46-12 | GD02108 | ST.. | 2 | | D41349J | 19 | | | 009 |
| 5066Z | | | AD | | 0-0 | 34-46-12 | D41349J | 19 | | | GD02108 | ST.. | 2 | | 115-199 |
| 5067B | 24 | G2 | AE | | 2-8 | 34-46-12 | D00433B | B13 | | | D41433J | 10 | | | 001-099 |
| 5067B | 24 | G2 | AE | | 3-0 | 34-46-12 | D41433J | 10 | | | D00433B | B13 | | | 115-199 |
| 5067R | 24 | G2 | AE | | 0-0 | 34-46-12 | D00433B | A13 | | | D41433J | 9 | | | 001-099 |
| 5067R | 24 | G2 | AE | | 0-0 | 34-46-12 | D41433J | 9 | | | D00433B | A13 | | | 115-199 |
| 5067Z | | | AE | | 0-0 | 34-46-12 | D00433B | DED | | | D41433J | | | AE | 001-099 |
| 5067Z | | | AE | | 0-0 | 34-46-12 | D41433J | | | AE | D00433B | DED | | | 115-199 |
| 5068B | 24 | G2 | AF | | 2-8 | 34-46-12 | D00433B | B06 | | | D41433J | 13 | | | 001-099 |
| 5068B | 24 | G2 | AF | | 3-0 | 34-46-12 | D41433J | 13 | | | D00433B | B06 | | | 115-199 |
| 5068R | 24 | G2 | AF | | 0-0 | 34-46-12 | D00433B | A06 | | | D41433J | 12 | | | 001-099 |
| 5068R | 24 | G2 | AF | | 0-0 | 34-46-12 | D41433J | 12 | | | D00433B | A06 | | | 115-199 |
| 5068Z | | | AF | | 0-0 | 34-46-12 | D00433B | DED | | | D41433J | | | AF | 001-099 |
| 5068Z | | | AF | | 0-0 | 34-46-12 | D41433J | | | AF | D00433B | DED | | | 115-199 |
| 5069B | 24 | G2 | AG | | 2-8 | 34-46-12 | D00433B | B11 | | | D41433J | 16 | | | 001-099 |
| 5069B | 24 | G2 | AG | | 3-0 | 34-46-12 | D41433J | 16 | | | D00433B | B11 | | | 115-199 |
| 5069R | 24 | G2 | AG | | 0-0 | 34-46-12 | D00433B | A11 | | | D41433J | 15 | | | 001-099 |
| 5069R | 24 | G2 | AG | | 0-0 | 34-46-12 | D41433J | 15 | | | D00433B | A11 | | | 115-199 |
| 5069Z | | | AG | | 0-0 | 34-46-12 | D00433B | DED | | | D41433J | | | AG | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 143

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------|-------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | | |
| 5069Z | | | | AG | 0-0 | 34-46-12 | D41433J | | | | AG | D00433B | DED | | | 115-199 |
| 5070B | | 24 | G2 | GA | 2-3 | 34-61-12 | D41567J | 2 | | | | TB0205Z | 109 | BJ | | 001-099 |
| 5070B | | 24 | G2 | GA | 3-0 | 34-61-12 | TB0205Z | 109 | BJ | | | D41567J | 2 | | | 115-199 |
| 5070R | | 24 | G2 | GA | 0-0 | 34-61-12 | D41567J | 1 | | | | TB0205Z | 110 | BJ | | 001-099 |
| 5070R | | 24 | G2 | GA | 0-0 | 34-61-12 | TB0205Z | 110 | BJ | | | D41567J | 1 | | | 115-199 |
| 5070Z | | | | GA | 0-0 | 34-61-12 | D41567J | 3 | | | | GD02114 | ST.. | 2 | | 001-099 |
| 5070Z | | | | GA | 0-0 | 34-61-12 | GD02114 | ST.. | 2 | | | D41567J | 3 | | | 115-199 |
| 5071B | | 24 | G2 | DM | 3-9 | 22-12-21 | D00085D | B01 | | | | D41605J | 43 | | | 001-099 |
| 5071B | | 24 | G2 | DM | 3-0 | 22-12-21 | D41605J | 43 | | | | D00085D | B01 | | | 115-199 |
| 5071R | | 24 | G2 | DM | 0-0 | 22-12-21 | D00085D | A01 | | | | D41605J | 42 | | | 001-099 |
| 5071R | | 24 | G2 | DM | 0-0 | 22-12-21 | D41605J | 42 | | | | D00085D | A01 | | | 115-199 |
| 5071Z | | | | DM | 0-0 | 22-12-21 | D00085D | DED | | | | D41605J | | | DM | 001-099 |
| 5071Z | | | | DM | 0-0 | 22-12-21 | D41605J | | | DM | | D00085D | DED | | | 115-199 |
| 5072B | | 24 | G2 | AH | 3-0 | SPARE | D00433B | D01 | | | | D41433J | 18 | | | 115-199 |
| 5072R | | 24 | G2 | AH | 0-0 | SPARE | D00433B | C01 | | | | D41433J | 19 | | | 115-199 |
| 5072Z | | | | AH | 0-0 | SPARE | D00433B | DED | | | | D41433J | | | AH | 115-199 |
| 5073B | | 24 | G2 | AI | 2-8 | 22-22-11 | D41815J | 4 | | | | TB0205Y | A075 | BJ | | 001-099 |
| 5073B | | 24 | G2 | AI | 4-0 | 22-22-11 | D41815J | 4 | | | | TB0205Y | A075 | BJ | | 115-199 |
| 5073R | | 24 | G2 | AI | 0-0 | 22-22-11 | D41815J | 3 | | | | TB0205Y | A076 | BJ | | ALL |
| 5073Z | | | | AI | 0-0 | 22-22-11 | D41815J | 5 | | | | GD02110 | ST.. | 2 | | ALL |
| 5074B | | 24 | G2 | GJ | 4-10 | 34-24-11 | D00447A | B01 | | | | TB0205Y | C101 | BJ | | 001-099 |
| 5074B | | 24 | G2 | GJ | 6-0 | 34-24-11 | TB0205Y | C101 | BJ | | | D00447A | B01 | | | 115-199 |
| 5074R | | 24 | G2 | GJ | 0-0 | 34-24-11 | D00447A | A01 | | | | TB0205Y | C102 | BJ | | 001-099 |
| 5074R | | 24 | G2 | GJ | 0-0 | 34-24-11 | TB0205Y | C102 | BJ | | | D00447A | A01 | | | 115-199 |
| 5074Z | | | | GJ | 0-0 | 34-24-11 | D00447A | DED | | | | GD02114 | ST.. | 2 | | 001-099 |
| 5074Z | | | | GJ | 0-0 | 34-24-11 | GD02114 | ST.. | 2 | | | D00447A | DED | | | 115-199 |
| 5075B | | 24 | G2 | GK | 5-0 | 34-31-31 | D00207B | C11 | | | | TB0205Y | C101 | BJ | | 001-099 |
| 5075B | | 24 | G2 | GK | 6-0 | 34-31-31 | TB0205Y | C101 | BJ | | | D02943B | H01 | | | 115-199 |
| 5075R | | 24 | G2 | GK | 0-0 | 34-31-31 | D00207B | B11 | | | | TB0205Y | C102 | BJ | | 001-099 |
| 5075R | | 24 | G2 | GK | 0-0 | 34-31-31 | TB0205Y | C102 | BJ | | | D02943B | G01 | | | 115-199 |
| 5075Z | | | | GK | 0-0 | 34-31-31 | D00207B | DED | | | | GD02114 | ST.. | 2 | | 001-099 |
| 5075Z | | | | GK | 0-0 | 34-31-31 | GD02114 | ST.. | 2 | | | D02943B | DED | | | 115-199 |
| 5077B | | 24 | Y2 | CU | 5-0 | 34-22-38 | D00085A | B03 | | | | D41643J | 19 | | | 115-199 |
| 5077R | | 24 | Y2 | CU | 0-0 | 34-22-38 | D00085A | A03 | | | | D41643J | 10 | | | 115-199 |
| 5077Z | | | | CU | 0-0 | 34-22-38 | D00085A | DED | | | | D41643J | | | CU | 115-199 |
| 5078B | | 24 | G2 | GX | 3-7 | 34-25-11 | D00919A | D08 | | | | TB0205Y | A067 | BJ | | 001, 003-099 |
| 5078B | | 24 | G2 | EE | 4-0 | 34-25-11 | D00919A | D08 | | | | TB0205Y | A067 | BJ | | 115-199 |
| 5078R | | 24 | G2 | GX | 0-0 | 34-25-11 | D00919A | C08 | | | | TB0205Y | A068 | BJ | | 001, 003-099 |
| 5078R | | 24 | G2 | EE | 0-0 | 34-25-11 | D00919A | C08 | | | | TB0205Y | A068 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 144

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1170
Page 145
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5085B | 24 | | G2 | GG | 2-1 | 34-22-38 | D41395J | | 2 | | TB0205Z | 55 | BJ | | 001-099 |
| 5085B | 24 | | G2 | GG | 4-0 | 34-22-38 | D41395J | | 2 | | TB0205Z | 55 | BJ | | 115-199 |
| 5085R | 24 | | G2 | GG | 0-0 | 34-22-38 | D41395J | | 1 | | TB0205Z | 56 | BJ | | ALL |
| 5085Z | | | | GG | 0-0 | 34-22-38 | D41395J | | 3 | | GD02108 | ST.. | 2 | | ALL |
| 5086B | 24 | | G2 | LJ | 3-5 | 31-31-43 | D41815J | | 26 | | TB0205Y | C101 | BJ | | 001-099 |
| 5086B | 24 | | G2 | FF | 4-0 | 31-31-22 | D41815J | | 27 | | TB0205Y | C101 | BJ | | 115-199 |
| 5086R | 24 | | G2 | LJ | 0-0 | 31-31-43 | D41815J | | 25 | | TB0205Y | C102 | BJ | | 001-099 |
| 5086R | 24 | | G2 | FF | 0-0 | 31-31-22 | D41815J | | 26 | | TB0205Y | C102 | BJ | | 115-199 |
| 5086Z | | | | LJ | 0-0 | 31-31-43 | D41815J | | 27 | | GD02114 | ST.. | 2 | | 001-099 |
| 5086Z | | | | FF | 0-0 | 31-31-22 | D41815J | | 25 | | GD02114 | ST.. | 2 | | 115-199 |
| 5087B | 24 | | G2 | FI | 2-10 | 34-46-12 | D00433B | | D13 | | TB0205Y | A065 | BJ | | 009 |
| 5087B | 24 | | G2 | FI | 3-0 | 34-46-12 | D00433B | | D13 | | TB0205Y | A065 | BJ | | 115-199 |
| 5087R | 24 | | G2 | FI | 0-0 | 34-46-12 | D00433B | | C13 | | TB0205Y | A066 | BJ | | 009, 115-199 |
| 5087Z | | | | FI | 0-0 | 34-46-12 | D00433B | | DED | | GD02109 | ST.. | 2 | | 009, 115-199 |
| 5088B | 24 | | G2 | FJ | 3-1 | 34-46-12 | D41433J | | 49 | | TB0205Y | A065 | BJ | | 009 |
| 5088B | 24 | | G2 | FJ | 4-0 | 34-46-12 | D41433J | | 49 | | TB0205Y | A065 | BJ | | 115-199 |
| 5088R | 24 | | G2 | FJ | 0-0 | 34-46-12 | D41433J | | 48 | | TB0205Y | A066 | BJ | | 009, 115-199 |
| 5088Z | | | | FJ | 0-0 | 34-46-12 | D41433J | | 50 | | GD02109 | ST.. | 2 | | 009, 115-199 |
| 5089B | 24 | | G2 | FK | 2-5 | 22-12-31 | D00055A | | B10 | | D41815J | 28 | | | 001-099 |
| 5089B | 24 | | G2 | FK | 2-0 | 22-12-31 | D41815J | | 28 | | D00055A | B10 | | | 115-199 |
| 5089R | 24 | | G2 | FK | 0-0 | 22-12-31 | D00055A | | A10 | | D41815J | 29 | | | 001-099 |
| 5089R | 24 | | G2 | FK | 0-0 | 22-12-31 | D41815J | | 29 | | D00055A | A10 | | | 115-199 |
| 5089Z | | | | FK | 0-0 | 22-12-31 | D00055A | | DED | | D41815J | | | FK | 001-099 |
| 5089Z | | | | FK | 0-0 | 22-12-31 | D41815J | | | FK | D00055A | DED | | | 115-199 |
| 5090B | 24 | | G2 | FG | 3-8 | 34-22-91 | D42063J | | 17 | | D41097J | 54 | | | 001-099 |
| 5090R | 24 | | G2 | FG | 0-0 | 34-22-91 | D42063J | | 16 | | D41097J | 53 | | | 001-099 |
| 5090Z | | | | FG | 0-0 | 34-22-91 | D42063J | | 18 | | D41097J | 55 | | | 001-099 |
| 5091B | 24 | | G2 | IC | 4-11 | 22-33-11 | D00383B | | K11 | | D41643J | 15 | | | 001-099 |
| 5091B | 24 | | G2 | IC | 5-0 | 22-33-11 | D00383B | | K11 | | D41643J | 15 | | | 115-199 |
| 5091R | 24 | | G2 | IC | 0-0 | 22-33-11 | D00383B | | J11 | | D41643J | 14 | | | ALL |
| 5091Z | | | | IC | 0-0 | 22-33-11 | D00383B | | DED | | D41643J | | | IC | ALL |
| 5093B | 24 | | G2 | FN | 4-0 | 34-22-93 | D42063J | | 17 | | D41097J | 54 | | | 115-199 |
| 5093R | 24 | | G2 | FN | 0-0 | 34-22-93 | D42063J | | 16 | | D41097J | 53 | | | 115-199 |
| 5093Z | | | | FN | 0-0 | 34-22-93 | D42063J | | 18 | | D41097J | 55 | | | 115-199 |
| 5094B | 24 | | G2 | HZ | 4-5 | 22-33-11 | D00383B | | B10 | | D41349J | 48 | | | 001-099 |
| 5094B | 24 | | G2 | HM | 4-0 | 22-33-11 | D00383B | | B10 | | D41349J | 48 | | | 115-199 |
| 5094R | 24 | | G2 | HZ | 0-0 | 22-33-11 | D00383B | | B09 | | D41349J | 47 | | | 001-099 |
| 5094R | 24 | | G2 | HM | 0-0 | 22-33-11 | D00383B | | B09 | | D41349J | 47 | | | 115-199 |
| 5094Z | | | | HZ | 0-0 | 22-33-11 | D00383B | | DED | | D41349J | | | GO | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 146

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5094Z | | | | HM | 0-0 | 22-33-11 | D00383B | DED | | | D41349J | | | GO | 115-199 |
| 5095B | 24 | G2 | | IA | 5-0 | 22-33-11 | D00383A | B06 | | | D41643J | 12 | | | 001-099 |
| 5095B | 24 | G2 | | HN | 5-0 | 22-33-11 | D00383A | B06 | | | D41643J | 12 | | | 115-199 |
| 5095R | 24 | G2 | | IA | 0-0 | 22-33-11 | D00383A | B05 | | | D41643J | 11 | | | 001-099 |
| 5095R | 24 | G2 | | HN | 0-0 | 22-33-11 | D00383A | B05 | | | D41643J | 11 | | | 115-199 |
| 5095Z | | | | IA | 0-0 | 22-33-11 | D00383A | DED | | | D41643J | | | GP | 001-099 |
| 5095Z | | | | HN | 0-0 | 22-33-11 | D00383A | DED | | | D41643J | | | GP | 115-199 |
| 5098B | 24 | G2 | | ID | 4-5 | 22-33-11 | D00383B | A12 | | | D41349J | 52 | | | 001-099 |
| 5098B | 24 | G2 | | ID | 4-0 | 22-33-11 | D00383B | A12 | | | D41349J | 52 | | | 115-199 |
| 5098R | 24 | G2 | | ID | 0-0 | 22-33-11 | D00383B | A11 | | | D41349J | 51 | | | ALL |
| 5098Z | | | | ID | 0-0 | 22-33-11 | D00383B | DED | | | D41349J | | | ID | ALL |
| 5099B | 24 | G2 | | IM | 2-8 | 34-46-12 | D00433B | D10 | | | D41433J | 54 | | | 001-099 |
| 5099B | 24 | G2 | | IM | 3-0 | 34-46-12 | D00433B | D10 | | | D41433J | 54 | | | 115-199 |
| 5099R | 24 | G2 | | IM | 0-0 | 34-46-12 | D00433B | C10 | | | D41433J | 53 | | | ALL |
| 5099Z | | | | IM | 0-0 | 34-46-12 | D00433B | DED | | | D41433J | | | IE | ALL |
| 5101B | 24 | G2 | | KA | 3-11 | 34-46-12 | D41097J | 45 | | | TB0205Z | 103 | BJ | | 001-099 |
| 5101B | 24 | G2 | | KA | 5-0 | 34-46-12 | D41097J | 45 | | | TB0205Z | 103 | BJ | | 115-199 |
| 5101R | 24 | G2 | | KA | 0-0 | 34-46-12 | D41097J | 44 | | | TB0205Z | 104 | BJ | | ALL |
| 5101Z | | | | KA | 0-0 | 34-46-12 | D41097J | 46 | | | GD02113 | ST.. | 2 | | ALL |
| 5102B | 24 | G2 | | KB | 4-0 | 34-46-12 | D00433B | D12 | | | TB0205Z | 103 | BJ | | 001-099 |
| 5102B | 24 | G2 | | KB | 5-0 | 34-46-12 | D00433B | D12 | | | TB0205Z | 103 | BJ | | 115-199 |
| 5102R | 24 | G2 | | KB | 0-0 | 34-46-12 | D00433B | C12 | | | TB0205Z | 104 | BJ | | ALL |
| 5102Z | | | | KB | 0-0 | 34-46-12 | D00433B | DED | | | GD02113 | ST.. | 2 | | ALL |
| 5103B | 24 | G2 | | KC | 4-1 | 34-46-12 | D41349J | 54 | | | TB0205Z | 105 | BJ | | 001-099 |
| 5103B | 24 | G2 | | KC | 5-0 | 34-46-12 | D41349J | 54 | | | TB0205Z | 105 | BJ | | 115-199 |
| 5103R | 24 | G2 | | KC | 0-0 | 34-46-12 | D41349J | 53 | | | TB0205Z | 106 | BJ | | ALL |
| 5103Z | | | | KC | 0-0 | 34-46-12 | D41349J | 55 | | | GD02113 | ST.. | 2 | | ALL |
| 5104B | 24 | G2 | | KD | 4-1 | 34-46-12 | D00433A | D09 | | | TB0205Z | 105 | BJ | | 001-099 |
| 5104B | 24 | G2 | | KD | 5-0 | 34-46-12 | D00433A | D09 | | | TB0205Z | 105 | BJ | | 115-199 |
| 5104R | 24 | G2 | | KD | 0-0 | 34-46-12 | D00433A | C09 | | | TB0205Z | 106 | BJ | | ALL |
| 5104Z | | | | KD | 0-0 | 34-46-12 | D00433A | DED | | | GD02113 | ST.. | 2 | | ALL |
| 5105B | 24 | G2 | | KE | 2-3 | 34-22-19 | D41567J | 49 | | | TB0205Z | 103 | BJ | | 001-099 |
| 5105B | 24 | G2 | | KE | 3-0 | 34-22-19 | D41567J | 49 | | | TB0205Z | 103 | BJ | | 115-199 |
| 5105R | 24 | G2 | | KE | 0-0 | 34-22-19 | D41567J | 48 | | | TB0205Z | 104 | BJ | | ALL |
| 5105Z | | | | KE | 0-0 | 34-22-19 | D41567J | 45 | | | GD02113 | ST.. | 2 | | ALL |
| 5106B | 24 | G2 | | KF | 3-11 | 34-22-29 | D41097J | 33 | | | TB0205Z | 105 | BJ | | 001-099 |
| 5106B | 24 | G2 | | KF | 5-0 | 34-22-29 | D41097J | 33 | | | TB0205Z | 105 | BJ | | 115-199 |
| 5106R | 24 | G2 | | KF | 0-0 | 34-22-29 | D41097J | 32 | | | TB0205Z | 106 | BJ | | ALL |
| 5106Z | | | | KF | 0-0 | 34-22-29 | D41097J | 34 | | | GD02113 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 147

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|-------------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5107B | 24 | G2 | KG | | 2-9 | 34-22-39 | D00085D | B07 | | | TB0205Z | 105 | BJ | | 001-099 |
| 5107B | 24 | G2 | KG | | 3-0 | 34-22-39 | D00085D | B07 | | | TB0205Z | 105 | BJ | | 115-199 |
| 5107R | 24 | G2 | KG | | 0-0 | 34-22-39 | D00085D | A07 | | | TB0205Z | 106 | BJ | | ALL |
| 5107Z | | | KG | | 0-0 | 34-22-39 | D00085D | DED | | | GD02113 | ST.. | 2 | | ALL |
| 5108B | 24 | G2 | KH | | 2-9 | 34-22-39 | D00085A | B07 | | | TB0205Z | 103 | BJ | | 001-099 |
| 5108B | 24 | G2 | KH | | 3-0 | 34-22-39 | D00085A | B07 | | | TB0205Z | 103 | BJ | | 115-199 |
| 5108R | 24 | G2 | KH | | 0-0 | 34-22-39 | D00085A | A07 | | | TB0205Z | 104 | BJ | | ALL |
| 5108Z | | | KH | | 0-0 | 34-22-39 | D00085A | DED | | | GD02113 | ST.. | 2 | | ALL |
| 5109B | 24 | G2 | JA | | 3-3 | 34-45-01 | D41815J | 16 | | | D00085A | K09 | | | 001-099 |
| 5109B | 24 | G2 | JA | | 4-0 | 34-45-01 | D41815J | 16 | | | D00085A | REF | VM | | 115-199 |
| 5109R | 24 | G2 | JA | | 0-0 | 34-45-01 | D41815J | 15 | | | D00085A | J09 | | | 001-099 |
| 5109R | 24 | G2 | JA | | 0-0 | 34-45-01 | D41815J | 15 | | | D00085A | REF | VM | | 115-199 |
| 5109Z | | | JA | | 0-0 | 34-45-01 | D41815J | | | JA | D00085A | DED | | | ALL |
| 5110B | 24 | G2 | JF | | 2-9 | 22-13-11 | D41643J | 34 | | | D00203B | C07 | | | 001-099 |
| 5110B | 24 | G2 | KQ | | 3-0 | 22-13-11 | D41643J | 34 | | | D02939B | B01 | | | 115-199 |
| 5110R | 24 | G2 | JF | | 0-0 | 22-13-11 | D41643J | 33 | | | D00203B | B07 | | | 001-099 |
| 5110R | 24 | G2 | KQ | | 0-0 | 22-13-11 | D41643J | 33 | | | D02939B | A01 | | | 115-199 |
| 5110Z | | | JF | | 0-0 | 22-13-11 | D41643J | | | JF | D00203B | DED | | | 001-099 |
| 5110Z | | | KQ | | 0-0 | 22-13-11 | D41643J | | | JF | D02939B | DED | | | 115-199 |
| 5111B | 24 | G2 | JB | | 2-7 | 34-31-11 | D42105J | 14 | | | TB0205Y | A015 | BJ | | 001-099 |
| 5111B | 24 | G2 | JB | | 5-0 | 34-31-11 | D42105J | 14 | | | TB0205Y | A015 | BJ | | 115-199 |
| 5111R | 24 | G2 | JB | | 0-0 | 34-31-11 | D42105J | 13 | | | TB0205Y | A016 | BJ | | ALL |
| 5111Z | | | JB | | 0-0 | 34-31-11 | D42105J | 12 | | | GD02103 | ST.. | 2 | *1 | ALL |
| 5112B | 24 | G2 | JC | | 2-4 | 34-31-11 | D00203B | C13 | | | TB0205Y | A015 | BJ | | 001-099 |
| 5112B | 24 | G2 | JC | | 3-0 | 34-31-11 | D02939B | K01 | | | TB0205Y | A015 | BJ | | 115-199 |
| 5112R | 24 | G2 | JC | | 0-0 | 34-31-11 | D00203B | B13 | | | TB0205Y | A016 | BJ | | 001-099 |
| 5112R | 24 | G2 | JC | | 0-0 | 34-31-11 | D02939B | J01 | | | TB0205Y | A016 | BJ | | 115-199 |
| 5112Z | | | JC | | 0-0 | 34-31-11 | D00203B | DED | | | GD02103 | ST.. | 2 | *1 | 001-099 |
| 5112Z | | | JC | | 0-0 | 34-31-11 | D02939B | DED | | | GD02103 | ST.. | 2 | *1 | 115-199 |
| 5113B | 24 | G2 | JD | | 3-8 | 34-31-11 | D42021J | 25 | | | TB0205Y | A015 | BJ | | 001-099 |
| 5113B | 24 | G2 | JD | | 5-0 | 34-31-11 | D42021J | 25 | | | TB0205Y | A015 | BJ | | 115-199 |
| 5113R | 24 | G2 | JD | | 0-0 | 34-31-11 | D42021J | 24 | | | TB0205Y | A016 | BJ | | ALL |
| 5113Z | | | JD | | 0-0 | 34-31-11 | D42021J | 26 | | | GD02103 | ST.. | 2 | *2 | ALL |
| 5114B | 24 | G2 | JE | | 2-9 | 34-31-11 | D00203B | C11 | | | D41643J | 37 | | | 001-099 |
| 5114B | 24 | G2 | JE | | 3-0 | 34-31-11 | D02939B | H01 | | | D41643J | 37 | | | 115-199 |
| 5114R | 24 | G2 | JE | | 0-0 | 34-31-11 | D00203B | B11 | | | D41643J | 36 | | | 001-099 |
| 5114R | 24 | G2 | JE | | 0-0 | 34-31-11 | D02939B | G01 | | | D41643J | 36 | | | 115-199 |
| 5114Z | | | JE | | 0-0 | 34-31-11 | D00203B | DED | | | D41643J | | | JE | 001-099 |
| 5114Z | | | JE | | 0-0 | 34-31-11 | D02939B | DED | | | D41643J | | | JE | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 148

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5115B | 24 | G2 | EY | | 3-3 | 34-45-01 | D00085D | K09 | | | D41815J | 43 | | | 003-099 |
| 5115R | 24 | G2 | EY | | 0-0 | 34-45-01 | D00085D | J09 | | | D41815J | 42 | | | 003-099 |
| 5115Z | | | EY | | 0-0 | 34-45-01 | D00085D | DED | | | D41815J | | | ET | 003-099 |
| 5116B | 22 | GU | MJ | | 4-0 | 34-25-12 | D41819J | 19 | | | TB0205Y | A067 | BJ | | 002 |
| 5116R | 22 | GU | MJ | | 0-0 | 34-25-12 | D41819J | 18 | | | TB0205Y | A068 | BJ | | 002 |
| 5116Z | | | MJ | | 0-0 | 34-25-12 | D41819J | 20 | | | GD02110 | ST.. | 2 | | 002 |
| 5118B | 22 | GU | ML | | 4-0 | 34-25-12 | D41819J | 22 | | | TB0205Y | C067 | BJ | | 002 |
| 5118R | 22 | GU | ML | | 0-0 | 34-25-12 | D41819J | 21 | | | TB0205Y | C068 | BJ | | 002 |
| 5118Z | | | ML | | 0-0 | 34-25-12 | D41819J | 23 | | | GD02109 | ST.. | 2 | | 002 |
| 5119B | 22 | GU | MS | | 4-0 | 34-25-12 | D41395J | 26 | | | TB0205Y | A063 | BJ | | 002 |
| 5119R | 22 | GU | MS | | 0-0 | 34-25-12 | D41395J | 25 | | | TB0205Y | A064 | BJ | | 002 |
| 5119Z | | | MS | | 0-0 | 34-25-12 | D41395J | 27 | | | GD02109 | ST.. | 2 | | 002 |
| 5120B | 22 | GU | MT | | 4-0 | 34-25-12 | D41395J | 54 | | | TB0205Y | C067 | BJ | | 002 |
| 5120R | 22 | GU | MT | | 0-0 | 34-25-12 | D41395J | 53 | | | TB0205Y | C068 | BJ | | 002 |
| 5120Z | | | MT | | 0-0 | 34-25-12 | D41395J | 55 | | | GD02109 | ST.. | 2 | | 002 |
| 5121B | 22 | GU | MU | | 4-0 | 34-25-12 | D00085D | D02 | | | TB0205Y | C067 | BJ | | 002 |
| 5121R | 22 | GU | MU | | 0-0 | 34-25-12 | D00085D | C02 | | | TB0205Y | C068 | BJ | | 002 |
| 5121Z | | | MU | | 0-0 | 34-25-12 | D00085D | DED | | | GD02109 | ST.. | 2 | | 002 |
| 5122B | 22 | GU | HS | | 4-0 | 34-25-12 | D41819J | 16 | | | TB0205Y | A067 | BJ | | 002 |
| 5122R | 22 | GU | HS | | 0-0 | 34-25-12 | D41819J | 15 | | | TB0205Y | A068 | BJ | | 002 |
| 5122Z | | | HS | | 0-0 | 34-25-12 | D41819J | 17 | | | GD02110 | ST.. | 2 | | 002 |
| 5123B | 22 | GU | MP | | 4-0 | 34-25-12 | D41823J | 8 | | | TB0205Y | A063 | BJ | | 002 |
| 5123R | 22 | GU | MP | | 0-0 | 34-25-12 | D41823J | 9 | | | TB0205Y | A064 | BJ | | 002 |
| 5123Z | | | MP | | 0-0 | 34-25-12 | D41823J | 10 | | | GD02109 | ST.. | 2 | | 002 |
| 5124B | 22 | GU | MR | | 4-0 | 34-25-12 | D00085A | D02 | | | TB0205Y | A063 | BJ | | 002 |
| 5124R | 22 | GU | MR | | 0-0 | 34-25-12 | D00085A | C02 | | | TB0205Y | A064 | BJ | | 002 |
| 5124Z | | | MR | | 0-0 | 34-25-12 | D00085A | DED | | | GD02109 | ST.. | 2 | | 002 |
| 5134B | 22 | GU | MA | | 3-0 | 34-46-12 | D41349J | 5 | | | D00433A | B08 | | | 002 |
| 5134R | 22 | GU | MA | | 0-0 | 34-46-12 | D41349J | 4 | | | D00433A | A08 | | | 002 |
| 5134Z | | | MA | | 0-0 | 34-46-12 | D41349J | | MA | | D00433A | DED | | | 002 |
| 5135B | 22 | GU | NN | | 4-0 | 34-46-12 | D00433B | B12 | | | D41395J | 47 | | | 002 |
| 5135R | 22 | GU | NN | | 0-0 | 34-46-12 | D00433B | A12 | | | D41395J | 46 | | | 002 |
| 5135Z | | | NN | | 0-0 | 34-46-12 | D00433B | DED | | | D41395J | | | NN | 002 |
| 5136B | 22 | GU | IJ | | 5-0 | 34-58-11 | D02939B | D02 | | | D41819J | 19 | | | 115-199 |
| 5136R | 22 | GU | IJ | | 0-0 | 34-58-11 | D02939B | C02 | | | D41819J | 18 | | | 115-199 |
| 5136Z | | | IJ | | 0-0 | 34-58-11 | D02939B | DED | | | D41819J | | | AB | 115-199 |
| 5137B | 22 | GU | IK | | 5-0 | 34-58-11 | D02939B | K02 | | | D41349J | 5 | | | 115-199 |
| 5137R | 22 | GU | IK | | 0-0 | 34-58-11 | D02939B | J02 | | | D41349J | 4 | | | 115-199 |
| 5137Z | | | IK | | 0-0 | 34-58-11 | D02939B | DED | | | D41349J | | | AI | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 149

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|-------------|---------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | | Splice |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5138B | 22 | GU | IL | | 5-0 | 34-58-11 | D02939B | B08 | | | D41643J | 5 | | | 115-199 |
| 5138R | 22 | GU | IL | | 0-0 | 34-58-11 | D02939B | A08 | | | D41643J | 4 | | | 115-199 |
| 5138Z | | | IL | | 0-0 | 34-58-11 | D02939B | DED | | | D41643J | | | AJ | 115-199 |
| 5139B | 22 | GU | IN | | 5-0 | 34-58-11 | D02939B | H08 | | | D41815J | 54 | | | 115-199 |
| 5139R | 22 | GU | IN | | 0-0 | 34-58-11 | D02939B | G08 | | | D41815J | 53 | | | 115-199 |
| 5139Z | | | IN | | 0-0 | 34-58-11 | D02939B | DED | | | D41815J | | | AK | 115-199 |
| 5146B | 22 | GU | MI | | 4-0 | 34-22-18 | D23005J | 20 | | | TB0205Y | A018 | BJ | | 002 |
| 5146R | 22 | GU | MI | | 0-0 | 34-22-18 | D23005J | 19 | | | TB0205Y | A017 | BJ | | 002 |
| 5146Z | | | MI | | 0-0 | 34-22-18 | D23005J | 21 | | | GD02103 | ST.. | 2 | | 002 |
| 5148B | 22 | GU | MC | | 4-0 | 34-22-28 | D23003J | 20 | | | TB0205Y | A018 | BJ | | 002 |
| 5148R | 22 | GU | MC | | 0-0 | 34-22-28 | D23003J | 19 | | | TB0205Y | A017 | BJ | | 002 |
| 5148Z | | | MC | | 0-0 | 34-22-28 | D23003J | 21 | | | GD02103 | ST.. | 2 | | 002 |
| 5149B | 22 | GU | ME | | 5-0 | 34-22-38 | D00085E | B14 | | | TB0205Y | A018 | BJ | | 002 |
| 5149R | 22 | GU | ME | | 0-0 | 34-22-38 | D00085E | A14 | | | TB0205Y | A017 | BJ | | 002 |
| 5149Z | | | ME | | 0-0 | 34-22-38 | D00085E | DED | | | GD02105 | ST.. | 2 | | 002 |
| 5150B | 22 | GU | IS | | 3-0 | 34-46-12 | D41349J | 15 | | | D00433A | A06 | | | 002 |
| 5150R | 22 | GU | IS | | 0-0 | 34-46-12 | D41349J | 14 | | | D00433A | A05 | | | 002 |
| 5150Z | | | IS | | 0-0 | 34-46-12 | D41349J | | | IS | D00433A | DED | | | 002 |
| 5152B | 22 | GU | IV | | 4-0 | 34-46-12 | D41433J | 34 | | | TB0205Z | 64 | BJ | | 002 |
| 5152R | 22 | GU | IV | | 0-0 | 34-46-12 | D41433J | 33 | | | TB0205Z | 63 | BJ | | 002 |
| 5152Z | | | IV | | 0-0 | 34-46-12 | D41433J | 35 | | | GD02108 | ST.. | 2 | | 002 |
| 5153B | 22 | GU | IT | | 3-0 | 34-46-12 | D41349J | 27 | | | D00433A | D01 | | | 002 |
| 5153R | 22 | GU | IT | | 0-0 | 34-46-12 | D41349J | 26 | | | D00433A | C01 | | | 002 |
| 5153Z | | | IT | | 0-0 | 34-46-12 | D41349J | | | IT | D00433A | DED | | | 002 |
| 5154B | 22 | GU | IW | | 4-0 | 34-46-12 | D41433J | 47 | | | TB0205Z | 64 | BJ | | 002 |
| 5154R | 22 | GU | IW | | 0-0 | 34-46-12 | D41433J | 46 | | | TB0205Z | 63 | BJ | | 002 |
| 5154Z | | | IW | | 0-0 | 34-46-12 | D41433J | 48 | | | GD02108 | ST.. | 2 | | 002 |
| 5155B | 22 | GU | IX | | 3-0 | 34-46-12 | D00433B | D01 | | | TB0205Z | 64 | BJ | | 002 |
| 5155R | 22 | GU | IX | | 0-0 | 34-46-12 | D00433B | C01 | | | TB0205Z | 63 | BJ | | 002 |
| 5155Z | | | IX | | 0-0 | 34-46-12 | D00433B | DED | | | GD02108 | ST.. | 2 | | 002 |
| 5156B | 24 | 7K | MF | | 4-0 | 34-46-14 | D23005J | 3 | | | D00433A | B03 | | | 002 |
| 5156W | 24 | 7K | MF | | 0-0 | 34-46-14 | D23005J | 2 | | | D00433A | A03 | | | 002 |
| 5156Z | | | MF | | 0-0 | 34-46-14 | D23005J | | | GX | D00433A | DED | | | 002 |
| 5157B | 24 | 7K | MG | | 4-0 | 34-46-14 | D23003J | 10 | | | D00433A | D03 | | | 002 |
| 5157W | 24 | 7K | MG | | 0-0 | 34-46-14 | D23003J | 9 | | | D00433A | C03 | | | 002 |
| 5157Z | | | MG | | 0-0 | 34-46-14 | D23003J | | | GZ | D00433A | DED | | | 002 |
| 5158B | 22 | GU | FQ | | 4-0 | 34-46-14 | D41819J | 12 | | | D00433A | D08 | | | 002 |
| 5158R | 22 | GU | FQ | | 0-0 | 34-46-14 | D41819J | 11 | | | D00433A | C08 | | | 002 |
| 5158Z | | | FQ | | 0-0 | 34-46-14 | D41819J | | | EE | D00433A | DED | | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 150

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| 5159B | 22 | GU | MD | | 4-0 | 34-22-38 | D00085D | D08 | | | TB0205Z | 64 | BJ | | 002 |
| 5159R | 22 | GU | MD | | 0-0 | 34-22-38 | D00085D | C08 | | | TB0205Z | 63 | BJ | | 002 |
| 5159Z | | | MD | | 0-0 | 34-22-38 | D00085D | DED | | | GD02108 | ST.. | 2 | | 002 |
| 5162B | 22 | GU | IY | | 3-0 | 34-58-11 | D00203B | REF | VM | | D00433B | REF | VM | | 002 |
| 5162R | 22 | GU | IY | | 0-0 | 34-58-11 | D00203B | REF | VM | | D00433B | REF | VM | | 002 |
| 5162Z | | | IY | | 0-0 | 34-58-11 | D00203B | DED | | | D00433B | DED | | | 002 |
| 5164B | 22 | GU | DJ | | 4-0 | 34-46-14 | D23005J | 14 | | | D00433B | B10 | | | 002 |
| 5164R | 22 | GU | DJ | | 0-0 | 34-46-14 | D23005J | 13 | | | D00433B | A10 | | | 002 |
| 5164Z | | | DJ | | 0-0 | 34-46-14 | D23005J | | | DJ | D00433B | DED | | | 002 |
| 5165B | 22 | GU | DR | | 4-0 | 34-46-14 | D23003J | 13 | | | D00433A | D05 | | | 002 |
| 5165R | 22 | GU | DR | | 0-0 | 34-46-14 | D23003J | 12 | | | D00433A | C05 | | | 002 |
| 5165Z | | | DR | | 0-0 | 34-46-14 | D23003J | | | DR | D00433A | DED | | | 002 |
| 5181B | 24 | G2 | LA | | 3-0 | 34-22-38 | D00085A | H06 | | | D41819J | 16 | | | 115-199 |
| 5181R | 24 | G2 | LA | | 0-0 | 34-22-38 | D00085A | G06 | | | D41819J | 15 | | | 115-199 |
| 5181Z | | | LA | | 0-0 | 34-22-38 | D00085A | DED | | | D41819J | | | LA | 115-199 |
| 5183B | 24 | G2 | LC | | 3-0 | 34-22-38 | D00085D | H06 | | | D41605J | 46 | | | 115-199 |
| 5183R | 24 | G2 | LC | | 0-0 | 34-22-38 | D00085D | G06 | | | D41605J | 45 | | | 115-199 |
| 5183Z | | | LC | | 0-0 | 34-22-38 | D00085D | DED | | | D41605J | | | LC | 115-199 |
| 5197B | 22 | GU | IU | | 3-0 | 34-46-12 | D41349J | 46 | | | D00433B | D06 | | | 002 |
| 5197R | 22 | GU | IU | | 0-0 | 34-46-12 | D41349J | 33 | | | D00433B | C06 | | | 002 |
| 5197Z | | | IU | | 0-0 | 34-46-12 | D41349J | | | IU | D00433B | DED | | | 002 |
| 5201B | 22 | GU | MH | | 4-0 | 34-58-21 | D41815J | 33 | | | D00433A | D11 | VM | | 002 |
| 5201R | 22 | GU | MH | | 0-0 | 34-58-21 | D41815J | 18 | | | D00433A | C11 | VM | | 002 |
| 5201Z | | | MH | | 0-0 | 34-58-21 | D41815J | 37 | | | D00433A | DED | | | 002 |
| 5203B | 24 | G2 | LH | | 2-4 | 31-31-42 | D41815J | 35 | | | D00055B | D02 | | | 001-099 |
| 5203R | 24 | G2 | LH | | 0-0 | 31-31-42 | D41815J | 34 | | | D00055B | D01 | | | 001-099 |
| 5203Z | | | LH | | 0-0 | 31-31-42 | D41815J | | | LH | D00055B | DED | | | 001-099 |
| 8002 | 22 | GA | | | 4-0 | 34-46-13 | D00433A | C10 | | | TB0205Y | C099 | BJ | | 002 |
| 8003 | 22 | GA | | | 5-0 | 34-46-13 | D00433A | A10 | | | TB0205Y | C042 | BJ | | 002 |
| 8004 | 22 | GA | | | 5-0 | 34-46-13 | D00433A | D04 | | | TB0205Y | C042 | BJ | | 002 |
| 8005 | 22 | GA | | | 4-0 | 34-46-13 | D00433A | C12 | | | TB0205X | A048 | BJ | | 002 |
| 8006 | 22 | GA | | | 4-0 | 34-46-13 | D00433A | B05 | | | TB0205Z | 116 | BJ | | 002 |
| 8007 | 22 | GA | | | 3-0 | 34-46-13 | D00433A | C02 | VM | | TB0205Z | 59 | BJ | | 002 |
| 8008 | 22 | GA | | | 3-0 | 34-46-13 | D00433A | D06 | VM | | TB0205Z | 57 | BJ | | 002 |
| 8009 | 22 | GA | | | 3-0 | 34-46-13 | D00433B | D04 | | | TB0205Z | 59 | BJ | | 002 |
| 8010 | 22 | GA | | | 3-0 | 34-46-13 | D00433B | A03 | | | TB0205Z | 57 | BJ | | 002 |
| 8011 | 22 | GA | | | 3-0 | 34-46-13 | D00433B | C08 | | | TB0205Z | 57 | BJ | | 002 |
| 8012 | 22 | GA | | | 3-0 | 34-46-13 | D00433B | D14 | | | TB0205Z | 57 | BJ | | 002 |
| 8014 | 22 | GA | | | 3-0 | 34-46-13 | D00433B | C04 | | | TB0205Z | 59 | BJ | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 151

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | |
| 8015 | 22 | | GA | 3-0 | 34-46-13 | D00433B | D15 | | | TB0205Z | 59 | BJ | | 002 |
| 8016 | 22 | | GA | 3-0 | 34-46-13 | D00433B | C02 | | | TB0205Z | 59 | BJ | | 002 |
| 8018 | 22 | | GA | 4-0 | 34-46-13 | D00433B | B07 | | | TB0205Z | 116 | BJ | | 002 |
| 8019 | 22 | | GA | 3-0 | 34-46-13 | D00433B | C15 | VM | | TB0205Z | 116 | BJ | | 002 |
| 8020 | 22 | | GA | 3-0 | 34-46-13 | D00433B | B04 | | | TB0205X | B048 | BJ | | 002 |
| 8021 | 22 | | GA | 3-0 | 34-46-13 | D00433B | A02 | | | TB0205X | B045 | BJ | | 002 |
| 8022 | 22 | | GA | 3-0 | 34-46-13 | D00433B | A05 | | | TB0205X | A047 | BJ | | 002 |
| 8023 | 22 | | GA | 3-0 | 34-46-13 | D00433B | A08 | | | TB0205X | A045 | BJ | | 002 |
| 8028 | 22 | | GA | 3-0 | 34-22-36 | D00085B | D02 | | | GD02112 | ST.. | 2 | | 002 |
| 8564 | 22 | | GA | 7-0 | 34-46-14 | D41819J | 14 | | | D00433A | B12 | | | 002 |
| FRAB | | | | 0-0 | 34-58-11 | D41819J | | | AB | D41819J | 20 | | | 115-199 |
| FRAC | | | | 0-0 | 34-46-12 | D41433J | 6 | | | D41433J | | | AC | 001-099 |
| FRAC | | | | 0-0 | 34-46-12 | D41433J | | | AC | D41433J | 6 | | | 115-199 |
| FRAD | | | | 0-0 | 34-46-12 | D41349J | 19 | | | D41349J | | | AD | 001-008, 010-099 |
| FRAE | | | | 0-0 | 34-46-12 | D41433J | 8 | | | D41433J | | | AE | 001-099 |
| FRAE | | | | 0-0 | 34-46-12 | D41433J | | | AE | D41433J | 8 | | | 115-199 |
| FRAF | | | | 0-0 | 34-46-12 | D41433J | 11 | | | D41433J | | | AF | 001-099 |
| FRAF | | | | 0-0 | 34-46-12 | D41433J | | | AF | D41433J | 11 | | | 115-199 |
| FRAG | | | | 0-0 | 34-46-12 | D41433J | 14 | | | D41433J | | | AG | 001-099 |
| FRAG | | | | 0-0 | 34-46-12 | D41433J | | | AG | D41433J | 14 | | | 115-199 |
| FRAH | | | | 0-0 | SPARE | D41433J | 20 | | | D41433J | | | AH | 115-199 |
| FRAI | | | | 0-0 | 34-58-11 | D41349J | | | AI | D41349J | 6 | | | 115-199 |
| FRAJ | | | | 0-0 | 34-58-11 | D41643J | | | AJ | D41643J | 24 | | | 115-199 |
| FRAK | | | | 0-0 | 34-58-11 | D41815J | | | AK | D41815J | 55 | | | 115-199 |
| FRAO | | | | 0-0 | 22-32-11 | D42063J | 3 | | | D42063J | | | AO | 001-099 |
| FRAO | | | | 0-0 | 22-32-11 | D42063J | | | AO | D42063J | 3 | | | 115-199 |
| FRAP | | | | 0-0 | 22-32-11 | D41819J | 4 | | | D41819J | | | AP | 001-099 |
| FRAP | | | | 0-0 | 22-32-11 | D41819J | | | AP | D41819J | 4 | | | 115-199 |
| FRAQ | | | | 0-0 | 22-32-11 | D41819J | 7 | | | D41819J | | | AQ | 001-099 |
| FRAQ | | | | 0-0 | 22-32-11 | D41819J | | | AQ | D41819J | 7 | | | 115-199 |
| FRAT | | | | 0-0 | 22-32-11 | D41349J | 12 | | | D41349J | | | AT | 001-099 |
| FRAT | | | | 0-0 | 22-32-11 | D41349J | | | AT | D41349J | 12 | | | 115-199 |
| FRAV | | | | 0-0 | 22-32-11 | D41823J | 3 | | | D41823J | | | AV | 001-099 |
| FRAV | | | | 0-0 | 22-32-11 | D41823J | | | AV | D41823J | 3 | | | 115-199 |
| FRAW | | | | 0-0 | 22-32-11 | D41823J | 6 | | | D41823J | | | AW | 001-099 |
| FRAW | | | | 0-0 | 22-32-11 | D41823J | | | AW | D41823J | 6 | | | 115-199 |
| FRBE | | | | 0-0 | 34-22-34 | D41605J | 9 | | | D41605J | | | BE | 001-099 |
| FRBE | | | | 0-0 | 34-22-34 | D41605J | | | BE | D41605J | 9 | | | 115-199 |
| FRBX | | | | 0-0 | 34-22-35 | D41567J | 27 | | | D41567J | | | BX | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 152

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1175 | 286N1175 | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | |
| FRBX | | | | 0-0 | 34-22-35 | D41567J | | | | BX | D41567J | 27 | | 115-199 |
| FRCQ | | | | 0-0 | 34-22-38 | D41349J | | 36 | | | D41349J | | CQ | 001-099 |
| FRCQ | | | | 0-0 | 34-22-38 | D41349J | | | | CQ | D41349J | 36 | | 115-199 |
| FRCR | | | | 0-0 | 34-22-38 | D41567J | | 30 | | | D41567J | | CR | 001-099 |
| FRCR | | | | 0-0 | 34-22-38 | D41567J | | | | CR | D41567J | 30 | | 115-199 |
| FRCT | | | | 0-0 | 34-22-38 | D41605J | | 26 | | | D41605J | | CT | 001-099 |
| FRCT | | | | 0-0 | 34-22-38 | D41815J | | | | CT | D41815J | 47 | | 115-199 |
| FRCU | | | | 0-0 | 34-22-38 | D41567J | | 15 | | | D41567J | | CU | 001-099 |
| FRCU | | | | 0-0 | 34-22-38 | D41643J | | 6 | | | D41643J | | CU | 115-199 |
| FRCV | | | | 0-0 | 34-22-39 | D41395J | | 6 | | | D41395J | | CV | 001-099 |
| FRCV | | | | 0-0 | 34-22-39 | D41395J | | | | CV | D41395J | 6 | | 115-199 |
| FRCW | | | | 0-0 | 34-22-39 | D41605J | | 27 | | | D41605J | | CW | 001-099 |
| FRCW | | | | 0-0 | 34-22-39 | D41605J | | | | CW | D41605J | 27 | | 115-199 |
| FRCX | | | | 0-0 | 34-22-39 | D41605J | | 30 | | | D41605J | | CX | 001-099 |
| FRCX | | | | 0-0 | 34-22-39 | D41605J | | | | CX | D41605J | 30 | | 115-199 |
| FRCY | | | | 0-0 | 34-22-39 | D41605J | | 33 | | | D41605J | | CY | 001-099 |
| FRCY | | | | 0-0 | 34-22-39 | D41605J | | | | CY | D41605J | 33 | | 115-199 |
| FRDB | | | | 0-0 | 34-22-39 | D41567J | | 18 | | | D41567J | | DB | 001-099 |
| FRDB | | | | 0-0 | 34-22-39 | D41567J | | | | DB | D41567J | 18 | | 115-199 |
| FRDC | | | | 0-0 | 34-22-39 | D41567J | | 21 | | | D41567J | | DC | 001-099 |
| FRDC | | | | 0-0 | 34-22-39 | D41567J | | | | DC | D41567J | 21 | | 115-199 |
| FRDD | | | | 0-0 | 34-22-39 | D41567J | | 24 | | | D41567J | | DD | 001-099 |
| FRDD | | | | 0-0 | 34-22-39 | D41567J | | | | DD | D41567J | 24 | | 115-199 |
| FRDJ | | | | 0-0 | 34-46-14 | D23005J | | | | DJ | D23005J | 15 | | 002 |
| FRDJ | | | | 0-0 | 34-25-11 | D41097J | | | | DJ | D41097J | 38 | | 115-199 |
| FRDL | | | | 0-0 | 22-12-11 | D41567J | | 41 | | | D41567J | | DL | ALL |
| FRDM | | | | 0-0 | 22-12-21 | D41605J | | 44 | | | D41605J | | DM | 001-099 |
| FRDM | | | | 0-0 | 22-12-21 | D41605J | | | | DM | D41605J | 44 | | 115-199 |
| FRDP | | | | 0-0 | 22-12-31 | D41395J | | 14 | | | D41395J | | DP | 001-099 |
| FRDP | | | | 0-0 | 22-12-31 | D41395J | | | | DP | D41395J | 14 | | 115-199 |
| FRDQ | | | | 0-0 | 22-12-31 | D41643J | | 9 | | | D41643J | | DQ | ALL |
| FRDR | | | | 0-0 | 34-46-14 | D23003J | | | | DR | D23003J | 14 | | 002 |
| FRDR | | | | 0-0 | 34-25-11 | D41349J | | | | DR | D41349J | 20 | | 115-199 |
| FREE | | | | 0-0 | 34-46-14 | D41819J | | | | EE | D41819J | 13 | | 002 |
| FREL | | | | 0-0 | 22-15-11 | D41395J | | 40 | | | D41395J | | EL | 001-099 |
| FREL | | | | 0-0 | 22-15-11 | D41395J | | | | EL | D41395J | 40 | | 115-199 |
| FREM | | | | 0-0 | 22-15-11 | D41349J | | 9 | | | D41349J | | EM | ALL |
| FREN | | | | 0-0 | 22-15-11 | D41097J | | 3 | | | D41097J | | EN | ALL |
| FREO | | | | 0-0 | 22-15-11 | D41395J | | 43 | | | D41395J | | EO | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 153

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|--------------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1175 | 286N1175 | | | | E2-3 INTEGRATION BUNDLE (continued) | | | | | | | | | | | |
| FREP | | | | | 0-0 | 22-41-12 | | D41097J | 28 | | | D41097J | | | EP | ALL |
| FREQ | | | | | 0-0 | 22-41-12 | | D41097J | 31 | | | D41097J | | | EQ | ALL |
| FRER | | | | | 0-0 | 22-41-11 | | D41815J | 9 | | | D41815J | | | ER | ALL |
| FRET | | | | | 0-0 | 34-45-01 | | D41815J | | | ET | D41815J | 44 | | | 003-099 |
| FRFD | | | | | 0-0 | 31-31-22 | | D41815J | | | FD | D41815J | 22 | | | 115-199 |
| FRFK | | | | | 0-0 | 22-12-31 | | D41815J | 30 | | | D41815J | | | FK | ALL |
| FRFP | | | | | 0-0 | 34-25-11 | | D41097J | | | FP | D41097J | 41 | | | 115-199 |
| FRFQ | | | | | 0-0 | 34-25-11 | | D41349J | | | FQ | D41349J | 23 | | | 115-199 |
| FRGN | | | | | 0-0 | 34-31-31 | | D42109J | 12 | | | D42109J | | | GN | 001-099 |
| FRGN | | | | | 0-0 | 34-31-31 | | D42109J | | | GN | D42109J | 12 | | | 115-199 |
| FRGO | | | | | 0-0 | 22-33-11 | | D41349J | 49 | | | D41349J | | | GO | ALL |
| FRGP | | | | | 0-0 | 22-33-11 | | D41643J | 13 | | | D41643J | | | GP | ALL |
| FRGV | | | | | 0-0 | 34-25-11 | | D41097J | 41 | | | D41097J | | | GV | 001, 003-099 |
| FRGW | | | | | 0-0 | 34-25-11 | | D41349J | 20 | | | D41349J | | | GW | 001, 003-099 |
| FRGX | | | | | 0-0 | 34-46-14 | | D23005J | | | GX | D23005J | 4 | | | 002 |
| FRGY | | | | | 0-0 | 34-25-11 | | D41097J | 38 | | | D41097J | | | GY | 001, 003-099 |
| FRGZ | | | | | 0-0 | 34-46-14 | | D23003J | | | GZ | D23003J | 11 | | | 002 |
| FRIC | | | | | 0-0 | 22-33-11 | | D41643J | 16 | | | D41643J | | | IC | 001-099 |
| FRIC | | | | | 0-0 | 22-33-11 | | D41643J | | | IC | D41643J | 16 | | | 115-199 |
| FRID | | | | | 0-0 | 22-33-11 | | D41349J | 50 | | | D41349J | | | ID | 001-099 |
| FRID | | | | | 0-0 | 22-33-11 | | D41349J | | | ID | D41349J | 50 | | | 115-199 |
| FRIE | | | | | 0-0 | 34-46-12 | | D41433J | 55 | | | D41433J | | | IE | ALL |
| FRIS | | | | | 0-0 | 34-46-12 | | D41349J | | | IS | D41349J | 16 | | | 002 |
| FRIT | | | | | 0-0 | 34-46-12 | | D41349J | | | IT | D41349J | 28 | | | 002 |
| FRIU | | | | | 0-0 | 34-46-12 | | D41349J | | | IU | D41349J | 29 | | | 002 |
| FRJA | | | | | 0-0 | 34-45-01 | | D41815J | | | JA | D41815J | 17 | | | ALL |
| FRJE | | | | | 0-0 | 34-31-11 | | D41643J | 38 | | | D41643J | | | JE | ALL |
| FRJF | | | | | 0-0 | 22-13-11 | | D41643J | | | JF | D41643J | 35 | | | ALL |
| FRLA | | | | | 0-0 | 34-22-38 | | D41819J | 17 | | | D41819J | | | LA | 115-199 |
| FRLC | | | | | 0-0 | 34-22-38 | | D41605J | 47 | | | D41605J | | | LC | 115-199 |
| FRLH | | | | | 0-0 | 31-31-42 | | D41815J | | | LH | D41815J | 36 | | | 001-099 |
| FRLI | | | | | 0-0 | 31-31-42 | | D41815J | | | LI | D41815J | 24 | | | 001, 003-099 |
| FRMA | | | | | 0-0 | 34-46-12 | | D41349J | | | MA | D41349J | 6 | | | 002 |
| FRNN | | | | | 0-0 | 34-46-12 | | D41395J | 48 | | | D41395J | | | NN | 002 |
| W1177 | 286N1177 | | | | E2-4 SHELF BUNDLE | | | | | | | | | | | |
| 0001 | 24 | | GK | | 2-0 | 34-21-11 | | D00137B | F02 | | | D42201J | 1 | | | ALL |
| 0002 | 24 | | GK | | 2-0 | 34-21-11 | | D00137B | F01 | | | D42201J | 2 | | | ALL |
| 0003 | 22 | | GA | | 2-0 | 34-21-11 | | D00137B | E13 | | | D42201J | 3 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 154

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1177 | 286N1177 | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | | |
| 0004 | 22 | | GA | | 2-0 | 34-21-11 | D00137B | E12 | | | SM00001 | | WI | | ALL | |
| 0005 | 22 | | GA | | 2-0 | 34-21-11 | D00137B | E11 | | | SM00002 | | WI | | ALL | |
| 0006 | 22 | | GA | | 2-0 | 34-21-11 | D00137B | E10 | | | SM00003 | | WI | | ALL | |
| 0007 | 22 | | GA | | 2-0 | 34-21-11 | D42201J | 4 | | | SM00001 | | WI | | 001-099 | |
| 0007 | 22 | | GA | | 2-0 | 34-21-11 | SM00001 | | WI | | D42201J | 4 | | | 115-199 | |
| 0008 | 22 | | GA | | 2-0 | 34-21-11 | D42201J | 5 | | | SM00002 | | WI | | 001-099 | |
| 0008 | 22 | | GA | | 2-0 | 34-21-11 | SM00002 | | WI | | D42201J | 5 | | | 115-199 | |
| 0009 | 22 | | GA | | 2-0 | 34-21-11 | D42201J | 6 | | | SM00003 | | WI | | 001-099 | |
| 0009 | 22 | | GA | | 2-0 | 34-21-11 | SM00003 | | WI | | D42201J | 6 | | | 115-199 | |
| 0010 | 22 | | GA | | 2-0 | 34-21-11 | D00137B | D01 | | | D42201J | 7 | | | ALL | |
| 0011 | 22 | | GA | | 2-0 | 34-21-11 | D00137B | D02 | | | D42201J | 8 | | | ALL | |
| 0012 | 22 | | GA | | 2-0 | 34-21-11 | D00137B | D03 | | | D42201J | 9 | | | ALL | |
| 0013 | 22 | | GA | | 2-0 | 22-21-11 | D00137B | E09 | | | D41099J | 4 | | | ALL | |
| 0015 | 24 | | GK | | 2-0 | 34-21-11 | SM00004 | | WI | | D42015J | 2 | | | ALL | |
| 0016 | 22 | | GA | | 2-0 | 34-21-11 | D41099J | 12 | | | SM00001 | | WI | | 001-099 | |
| 0016 | 22 | | GA | | 2-0 | 34-21-11 | SM00001 | | WI | | D41099J | 12 | | | 115-199 | |
| 0017 | 22 | | GA | | 2-0 | 34-21-11 | D41099J | 13 | | | SM00002 | | WI | | 001-099 | |
| 0017 | 22 | | GA | | 2-0 | 34-21-11 | SM00002 | | WI | | D41099J | 13 | | | 115-199 | |
| 0018 | 22 | | GA | | 2-0 | 34-21-11 | D41099J | 14 | | | SM00003 | | WI | | 001-099 | |
| 0018 | 22 | | GA | | 2-0 | 34-21-11 | SM00003 | | WI | | D41099J | 14 | | | 115-199 | |
| 0019 | 22 | | GA | | 3-0 | 34-21-21 | D41351J | 38 | | | SM00005 | | WI | | 001-099 | |
| 0019 | 22 | | GA | | 3-0 | 34-21-21 | SM00005 | | WI | | D41351J | 38 | | | 115-199 | |
| 0020 | 24 | | GK | | 2-0 | 34-21-21 | D00141B | F02 | | | D42203J | 1 | | | ALL | |
| 0021 | 24 | | GK | | 2-0 | 34-21-21 | D00141B | F01 | | | D42203J | 2 | | | ALL | |
| 0022 | 22 | | GA | | 2-0 | 34-21-21 | D00141B | E13 | | | D42203J | 3 | | | ALL | |
| 0023 | 22 | | GA | | 3-0 | 34-21-21 | D00141B | E12 | | | SM00005 | | WI | | ALL | |
| 0024 | 22 | | GA | | 3-0 | 34-21-21 | D42203J | 4 | | | SM00005 | | WI | | 001-099 | |
| 0024 | 22 | | GA | | 3-0 | 34-21-21 | SM00005 | | WI | | D42203J | 4 | | | 115-199 | |
| 0025 | 22 | | GA | | 3-0 | 34-21-21 | D00141B | E10 | | | SM00006 | | WI | | ALL | |
| 0026 | 22 | | GA | | 3-0 | 34-21-21 | D42203J | 5 | | | SM00006 | | WI | | 001-099 | |
| 0026 | 22 | | GA | | 3-0 | 34-21-21 | SM00006 | | WI | | D42203J | 5 | | | 115-199 | |
| 0027 | 22 | | GA | | 2-0 | 34-21-21 | D00141B | D01 | | | D42203J | 6 | | | ALL | |
| 0028 | 22 | | GA | | 2-0 | 34-21-21 | D00141B | D02 | | | D42203J | 7 | | | ALL | |
| 0029 | 22 | | GA | | 2-0 | 34-21-21 | D00141B | D03 | | | D42203J | 8 | | | ALL | |
| 0030 | 22 | | GA | | 3-0 | 34-21-21 | D00141B | E11 | | | SM00007 | | WI | | ALL | |
| 0031 | 22 | | GA | | 3-0 | 34-21-21 | D42203J | 9 | | | SM00007 | | WI | | 001-099 | |
| 0031 | 22 | | GA | | 3-0 | 34-21-21 | SM00007 | | WI | | D42203J | 9 | | | 115-199 | |
| 0032 | 22 | | GA | | 2-0 | 22-21-21 | D00141B | E09 | | | D41351J | 4 | | | ALL | |
| 0034 | 24 | | GK | | 3-0 | 34-21-21 | D00141B | J13 | | | D42089J | 1 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 155

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1177 | 286N1177 | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0035 | 22 | | GA | | 3-0 | 34-21-21 | D41351J | 40 | | | SM00007 | | WI | | 001-099 |
| 0035 | 22 | | GA | | 3-0 | 34-21-21 | SM00007 | | WI | | D41351J | 40 | | | 115-199 |
| 0036 | 22 | | GA | | 3-0 | 34-21-21 | D41351J | 39 | | | SM00006 | | WI | | 001-099 |
| 0036 | 22 | | GA | | 3-0 | 34-21-21 | SM00006 | | WI | | D41351J | 39 | | | 115-199 |
| 0038 | 24 | | GK | | 3-0 | 34-21-31 | D00139B | J13 | | | D42051J | 1 | | | ALL |
| 0039 | 24 | | GK | | 3-0 | 34-21-31 | D00139B | F02 | | | D42205J | 1 | | | ALL |
| 0040 | 24 | | GK | | 3-0 | 34-21-31 | D00139B | F01 | | | D42205J | 2 | | | ALL |
| 0041 | 22 | | GA | | 3-0 | 34-21-31 | D00139B | E13 | | | D42205J | 3 | | | ALL |
| 0042 | 22 | | GA | | 2-0 | 34-21-31 | D00139B | E12 | | | SM00009 | | WI | | ALL |
| 0043 | 22 | | GA | | 2-0 | 34-21-31 | D00139B | E11 | | | SM00010 | | WI | | ALL |
| 0044 | 22 | | GA | | 2-0 | 34-21-31 | D00139B | E10 | | | SM00011 | | WI | | ALL |
| 0045 | 22 | | GA | | 3-0 | 34-21-31 | D41397J | 7 | | | SM00009 | | WI | | 001-099 |
| 0045 | 22 | | GA | | 3-0 | 34-21-31 | SM00009 | | WI | | D41397J | 7 | | | 115-199 |
| 0046 | 22 | | GA | | 3-0 | 34-21-31 | D41397J | 8 | | | SM00010 | | WI | | 001-099 |
| 0046 | 22 | | GA | | 3-0 | 34-21-31 | SM00010 | | WI | | D41397J | 8 | | | 115-199 |
| 0047 | 22 | | GA | | 3-0 | 34-21-31 | D41397J | 9 | | | SM00011 | | WI | | 001-099 |
| 0047 | 22 | | GA | | 3-0 | 34-21-31 | SM00011 | | WI | | D41397J | 9 | | | 115-199 |
| 0048 | 22 | | GA | | 4-0 | 34-21-31 | D42205J | 4 | | | SM00009 | | WI | | 001-099 |
| 0048 | 22 | | GA | | 4-0 | 34-21-31 | SM00009 | | WI | | D42205J | 4 | | | 115-199 |
| 0049 | 22 | | GA | | 4-0 | 34-21-31 | D42205J | 5 | | | SM00010 | | WI | | 001-099 |
| 0049 | 22 | | GA | | 4-0 | 34-21-31 | SM00010 | | WI | | D42205J | 5 | | | 115-199 |
| 0050 | 22 | | GA | | 4-0 | 34-21-31 | D42205J | 6 | | | SM00011 | | WI | | 001-099 |
| 0050 | 22 | | GA | | 4-0 | 34-21-31 | SM00011 | | WI | | D42205J | 6 | | | 115-199 |
| 0051 | 22 | | GA | | 3-0 | 34-21-31 | D00139B | D01 | | | D42205J | 7 | | | ALL |
| 0052 | 22 | | GA | | 3-0 | 34-21-31 | D00139B | D02 | | | D42205J | 8 | | | ALL |
| 0053 | 22 | | GA | | 3-0 | 34-21-31 | D00139B | D03 | | | D42205J | 9 | | | ALL |
| 0054 | 22 | | GA | | 3-0 | 22-21-11 | D00139B | E09 | | | D41397J | 16 | | | ALL |
| 0055 | 24 | | GK | | 2-0 | 34-21-11 | SM00004 | | WI | | D00137B | J13 | | | ALL |
| 0056 | 24 | | GK | | 2-0 | 34-22-17 | SM00004 | | WI | | D41569J | 28 | | | 001-099 |
| 0056 | 24 | | GK | | 2-0 | 34-22-17 | SM00004 | | WI | | D41569J | 34 | | | 115-199 |
| 0057 | 24 | | GK | | 2-0 | 34-22-37 | SM00004 | | WI | | D41569J | 29 | | | 001-099 |
| 0057 | 24 | | GK | | 2-0 | 34-22-37 | SM00004 | | WI | | D41569J | 54 | | | 115-199 |
| 0061 | 22 | | GA | | 2-0 | 33-16-21 | D00137B | E08 | | | D42201J | 18 | | | ALL |
| 0062 | 22 | | GA | | 2-0 | 33-16-31 | D00141B | E08 | | | D42203J | 20 | | | ALL |
| 0063 | 22 | | GA | | 3-0 | 33-16-61 | D00139B | E08 | | | D42205J | 16 | | | ALL |
| 0066 | 20 | | GA | | 1-6 | 34-21-21 | D42203J | | | AT | GD02022 | ST.. | 2 | | ALL |
| 0067 | 20 | | GA | | 1-6 | 34-21-21 | D41351J | | | AZ | GD02022 | ST.. | 2 | | ALL |
| 0068 | 20 | | GA | | 1-6 | 34-21-21 | D41351J | | | BG | GD02022 | ST.. | 2 | | ALL |
| 0069 | 20 | | GA | | 1-6 | 34-21-31 | D42205J | | | BN | GD02029 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 156

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1177 | 286N1177 | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0071 | 20 | | GA | | 1-6 | 34-21-11 | D42201J | | | AB | GD02029 | ST.. | 2 | | ALL |
| 0072 | 20 | | GA | | 3-0 | 34-21-31 | D00139C | 1 | | | D41397J | 20 | | | 001-099 |
| 0072 | 24 | | GK | | 3-0 | 34-21-31 | D41397J | 20 | | | TB0221Y | A039 | BJ | | 115-199 |
| 0073 | 20 | | GA | | 1-6 | 34-21-11 | D41569J | | | AI | GD02029 | ST.. | 2 | | ALL |
| 0098 | 20 | | GA | | 3-0 | 34-21-21 | D41001J | | | AS | GD02025 | ST.. | 2 | | ALL |
| 0101 | 20 | | GA | | 3-0 | 34-21-11 | D00137C | 5 | | | GD02030 | AC.. | 2 | | 001-099 |
| 0102 | 14 | | GA | | 2-0 | 34-21-11 | D00137C | 8 | | | GD02031 | DC.. | E | | 001-099 |
| 0103 | 16 | | GA | | 3-0 | 34-21-11 | D00137C | 11 | | | GD02030 | ST.. | 2 | | 001-099 |
| 0104 | 14 | | GA | | 4-0 | 34-21-11 | D00137C | 7 | | | D42225J | 1 | | | 001-099 |
| 0105 | 24 | | GK | | 3-0 | 34-21-11 | D00137C | 1 | | | D41758J | 2 | | | 001-099 |
| 0106 | 14 | | GA | | 2-0 | 34-21-21 | D00141C | 8 | | | GD02023 | DC.. | E | | 001-099 |
| 0107 | 14 | | GA | | 4-0 | 34-21-21 | D00141C | 7 | | | D42227J | 2 | | | 001-099 |
| 0108 | 16 | | GA | | 2-0 | 34-21-21 | D00141C | 11 | | | GD02020 | ST.. | 2 | | 001-099 |
| 0109 | 20 | | GA | | 2-0 | 34-21-21 | D00141C | 5 | | | GD02020 | AC.. | 2 | | 001-099 |
| 0110 | 20 | | GA | | 2-0 | 34-21-21 | D00141C | 1 | | | D41916J | 5 | | | 001-099 |
| 0111 | 14 | | GA | | 2-0 | 34-21-31 | D00139C | 8 | | | GD02027 | DC.. | E | | 001-099 |
| 0112 | 14 | | GA | | 3-0 | 34-21-31 | D00139C | 7 | | | D42229J | 3 | | | 001-099 |
| 0113 | 16 | | GA | | 3-0 | 34-21-31 | D00139C | 11 | | | GD02020 | ST.. | 2 | | 001-099 |
| 0114 | 20 | | GA | | 3-0 | 34-21-31 | D00139C | 5 | | | GD02020 | AC.. | 2 | | 001-099 |
| 0116 | 22 | | GA | | 1-0 | 34-21-11 | D00137B | K03 | | | D00137B | A01 | | | ALL |
| 0119 | 22 | | GA | | 1-0 | 34-21-21 | D00141B | A01 | | | D00141B | K03 | | | 001-099 |
| 0119 | 22 | | GA | | 1-0 | 34-21-21 | D00141B | K03 | | | D00141B | A01 | | | 115-199 |
| 0122 | 22 | | GA | | 1-0 | 34-21-31 | D00139B | A01 | | | D00139B | K03 | | | 001-099 |
| 0122 | 22 | | GA | | 1-0 | 34-21-31 | D00139B | K03 | | | D00139B | A01 | | | 115-199 |
| 5001B | 24 | | G2 | AA | 4-0 | 34-21-11 | D00137B | J11 | | | TB0221Y | C045 | BJ | | ALL |
| 5001R | 24 | | G2 | AA | 0-0 | 34-21-11 | D00137B | J10 | | | TB0221Y | A045 | BJ | | ALL |
| 5001Z | | | | AA | 0-0 | 34-21-11 | D00137B | DED | | | GD02025 | ST.. | 2 | | ALL |
| 5002B | 24 | | G2 | AB | 3-0 | 34-21-11 | D00137B | C06 | | | D42201J | 11 | | | 001-099 |
| 5002B | 24 | | G2 | AB | 2-0 | 34-21-11 | D00137B | C06 | | | D42201J | 11 | | | 115-199 |
| 5002R | 24 | | G2 | AB | 0-0 | 34-21-11 | D00137B | C05 | | | D42201J | 10 | | | ALL |
| 5002Z | | | | AB | 0-0 | 34-21-11 | D00137B | DED | | | D42201J | | | AB | ALL |
| 5003B | 24 | | G2 | AC | 3-0 | 34-21-11 | D00137B | C11 | | | TB0221Z | 80 | BJ | | ALL |
| 5003R | 24 | | G2 | AC | 0-0 | 34-21-11 | D00137B | C10 | | | TB0221Z | 79 | BJ | | ALL |
| 5003Z | | | | AC | 0-0 | 34-21-11 | D00137B | DED | | | GD02029 | ST.. | 2 | | ALL |
| 5004B | 24 | | G2 | AD | 3-0 | 34-21-11 | D42201J | 15 | | | TB0221Z | 80 | BJ | | 001-099 |
| 5004B | 24 | | G2 | AD | 3-0 | 34-21-11 | TB0221Z | 80 | BJ | | D42201J | 15 | | | 115-199 |
| 5004R | 24 | | G2 | AD | 0-0 | 34-21-11 | D42201J | 14 | | | TB0221Z | 79 | BJ | | 001-099 |
| 5004R | 24 | | G2 | AD | 0-0 | 34-21-11 | TB0221Z | 79 | BJ | | D42201J | 14 | | | 115-199 |
| 5004Z | | | | AD | 0-0 | 34-21-11 | D42201J | 16 | | | GD02029 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 157

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1177 | 286N1177 | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5004Z | | | | AD | 0-0 | 34-21-11 | GD02029 | ST.. | 2 | | D42201J | 16 | | | 115-199 |
| 5005B | 24 | G2 | | AE | 4-0 | 34-21-11 | D00137B | A14 | | | TB0221Y | C014 | BJ | | ALL |
| 5005R | 24 | G2 | | AE | 0-0 | 34-21-11 | D00137B | A13 | | | TB0221Y | A014 | BJ | | ALL |
| 5005Z | | | | AE | 0-0 | 34-21-11 | D00137B | DED | | | GD02021 | ST.. | 2 | | ALL |
| 5006B | 24 | G2 | | AF | 3-0 | 34-61-25 | D41351J | 9 | | | TB0221Y | C014 | BJ | | 001-099 |
| 5006B | 24 | G2 | | AF | 3-0 | 34-61-25 | TB0221Y | C014 | BJ | | D41351J | 9 | | | 115-199 |
| 5006R | 24 | G2 | | AF | 0-0 | 34-61-25 | D41351J | 8 | | | TB0221Y | A014 | BJ | | 001-099 |
| 5006R | 24 | G2 | | AF | 0-0 | 34-61-25 | TB0221Y | A014 | BJ | | D41351J | 8 | | | 115-199 |
| 5006Z | | | | AF | 0-0 | 34-61-25 | D41351J | 10 | | | GD02021 | ST.. | 2 | | 001-099 |
| 5006Z | | | | AF | 0-0 | 34-61-25 | GD02021 | ST.. | 2 | | D41351J | 10 | | | 115-199 |
| 5007B | 24 | G2 | | AG | 4-0 | 34-21-11 | D41569J | 10 | | | TB0221Z | 42 | BJ | | 001-099 |
| 5007B | 24 | G2 | | AG | 4-0 | 34-21-11 | TB0221Z | 42 | BJ | | D41569J | 10 | | | 115-199 |
| 5007R | 24 | G2 | | AG | 0-0 | 34-21-11 | D41569J | 11 | | | TB0221Z | 41 | BJ | | 001-099 |
| 5007R | 24 | G2 | | AG | 0-0 | 34-21-11 | TB0221Z | 41 | BJ | | D41569J | 11 | | | 115-199 |
| 5007Z | | | | AG | 0-0 | 34-21-11 | D41569J | 12 | | | GD02025 | ST.. | 2 | | 001-099 |
| 5007Z | | | | AG | 0-0 | 34-21-11 | GD02025 | ST.. | 2 | | D41569J | 12 | | | 115-199 |
| 5008B | 24 | G2 | | AH | 4-0 | 34-21-11 | D00137B | K05 | | | TB0221Z | 42 | BJ | | ALL |
| 5008R | 24 | G2 | | AH | 0-0 | 34-21-11 | D00137B | K04 | | | TB0221Z | 41 | BJ | | ALL |
| 5008Z | | | | AH | 0-0 | 34-21-11 | D00137B | DED | | | GD02025 | ST.. | 2 | | ALL |
| 5009B | 24 | G2 | | AI | 3-0 | 34-21-11 | D00137B | A09 | | | D41569J | 13 | | | 001-099 |
| 5009B | 24 | G2 | | AI | 2-0 | 34-21-11 | D00137B | A09 | | | D41569J | 13 | | | 115-199 |
| 5009R | 24 | G2 | | AI | 0-0 | 34-21-11 | D00137B | A08 | | | D41569J | 14 | | | ALL |
| 5009Z | | | | AI | 0-0 | 34-21-11 | D00137B | DED | | | D41569J | | | AI | ALL |
| 5010B | 22 | GU | | AJ | 3-0 | 32-42-11 | D41099J | 9 | | | TB0221Z | 80 | BJ | | 001-099 |
| 5010B | 24 | G2 | | AJ | 4-0 | 32-42-11 | TB0221Z | 80 | BJ | | D41099J | 9 | | | 115-199 |
| 5010R | 22 | GU | | AJ | 0-0 | 32-42-11 | D41099J | 10 | | | TB0221Z | 79 | BJ | | 001-099 |
| 5010R | 24 | G2 | | AJ | 0-0 | 32-42-11 | TB0221Z | 79 | BJ | | D41099J | 10 | | | 115-199 |
| 5010Z | | | | AJ | 0-0 | 32-42-11 | D41099J | 11 | | | GD02029 | ST.. | 2 | | 001-099 |
| 5010Z | | | | AJ | 0-0 | 32-42-11 | GD02029 | ST.. | 2 | | D41099J | 11 | | | 115-199 |
| 5011B | 24 | G2 | | AK | 3-0 | 22-21-11 | D41099J | 3 | | | TB0221Z | 82 | BJ | | 001-099 |
| 5011B | 24 | G2 | | AK | 3-0 | 22-21-11 | TB0221Z | 82 | BJ | | D41099J | 3 | | | 115-199 |
| 5011R | 24 | G2 | | AK | 0-0 | 22-21-11 | D41099J | 2 | | | TB0221Z | 81 | BJ | | 001-099 |
| 5011R | 24 | G2 | | AK | 0-0 | 22-21-11 | TB0221Z | 81 | BJ | | D41099J | 2 | | | 115-199 |
| 5011Z | | | | AK | 0-0 | 22-21-11 | D41099J | 1 | | | GD02029 | ST.. | 2 | | 001-099 |
| 5011Z | | | | AK | 0-0 | 22-21-11 | GD02029 | ST.. | 2 | | D41099J | 1 | | | 115-199 |
| 5012B | 24 | G2 | | AL | 3-0 | 34-22-91 | D41099J | 34 | | | TB0221Z | 80 | BJ | | 001-099 |
| 5012B | 24 | G2 | | AL | 3-0 | 34-22-93 | TB0221Z | 80 | BJ | | D41099J | 34 | | | 115-199 |
| 5012R | 24 | G2 | | AL | 0-0 | 34-22-91 | D41099J | 33 | | | TB0221Z | 79 | BJ | | 001-099 |
| 5012R | 24 | G2 | | AL | 0-0 | 34-22-93 | TB0221Z | 79 | BJ | | D41099J | 33 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 158

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1170
Page 159
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1177 | 286N1177 | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5020B | 24 | G2 | AT | | 2-0 | 34-21-21 | D00141B | C06 | | | D42203J | 11 | | | 115-199 |
| 5020R | 24 | G2 | AT | | 0-0 | 34-21-21 | D00141B | C05 | | | D42203J | 10 | | | ALL |
| 5020Z | | | AT | | 0-0 | 34-21-21 | D00141B | DED | | | D42203J | | | AT | ALL |
| 5021B | 24 | G2 | AU | | 3-0 | 34-21-21 | D00141B | C11 | | | TB0221Z | 16 | BJ | | ALL |
| 5021R | 24 | G2 | AU | | 0-0 | 34-21-21 | D00141B | C10 | | | TB0221Z | 15 | BJ | | ALL |
| 5021Z | | | AU | | 0-0 | 34-21-21 | D00141B | DED | | | GD02021 | ST.. | 2 | | ALL |
| 5022B | 24 | G2 | AV | | 3-0 | 34-21-21 | D42203J | 14 | | | TB0221Z | 16 | BJ | | 001-099 |
| 5022B | 24 | G2 | AV | | 3-0 | 34-21-21 | TB0221Z | 16 | BJ | | D42203J | 14 | | | 115-199 |
| 5022R | 24 | G2 | AV | | 0-0 | 34-21-21 | D42203J | 13 | | | TB0221Z | 15 | BJ | | 001-099 |
| 5022R | 24 | G2 | AV | | 0-0 | 34-21-21 | TB0221Z | 15 | BJ | | D42203J | 13 | | | 115-199 |
| 5022Z | | | AV | | 0-0 | 34-21-21 | D42203J | 15 | | | GD02021 | ST.. | 2 | | 001-099 |
| 5022Z | | | AV | | 0-0 | 34-21-21 | GD02021 | ST.. | 2 | | D42203J | 15 | | | 115-199 |
| 5023B | 24 | G2 | AW | | 3-0 | 34-21-21 | D00141B | A09 | | | TB0221Y | C043 | BJ | | ALL |
| 5023R | 24 | G2 | AW | | 0-0 | 34-21-21 | D00141B | A08 | | | TB0221Y | A043 | BJ | | ALL |
| 5023Z | | | AW | | 0-0 | 34-21-21 | D00141B | DED | | | GD02025 | ST.. | 2 | | ALL |
| 5024B | 24 | G2 | AX | | 3-0 | 34-21-21 | D00141B | K05 | | | D41351J | 12 | | | 001-099 |
| 5024B | 24 | G2 | AX | | 2-0 | 34-21-21 | D00141B | K05 | | | D41351J | 12 | | | 115-199 |
| 5024R | 24 | G2 | AX | | 0-0 | 34-21-21 | D00141B | K04 | | | D41351J | 11 | | | ALL |
| 5024Z | | | AX | | 0-0 | 34-21-21 | D00141B | DED | | | D41351J | | | BG | ALL |
| 5025B | 24 | G2 | AY | | 3-0 | 34-22-82 | D42015J | 6 | | | TB0221Z | 82 | BJ | | 001-099 |
| 5025B | 24 | G2 | AY | | 3-0 | 34-22-82 | TB0221Z | 82 | BJ | | D42015J | 6 | | | 115-199 |
| 5025R | 24 | G2 | AY | | 0-0 | 34-22-82 | D42015J | 5 | | | TB0221Z | 81 | BJ | | 001-099 |
| 5025R | 24 | G2 | AY | | 0-0 | 34-22-82 | TB0221Z | 81 | BJ | | D42015J | 5 | | | 115-199 |
| 5025Z | | | AY | | 0-0 | 34-22-82 | D42015J | 7 | | | GD02029 | ST.. | 2 | | 001-099 |
| 5025Z | | | AY | | 0-0 | 34-22-82 | GD02029 | ST.. | 2 | | D42015J | 7 | | | 115-199 |
| 5026B | 24 | G2 | AZ | | 3-0 | 34-21-21 | D00141B | A14 | | | D41351J | 15 | | | 001-099 |
| 5026B | 24 | G2 | AZ | | 2-0 | 34-21-21 | D00141B | A14 | | | D41351J | 15 | | | 115-199 |
| 5026R | 24 | G2 | AZ | | 0-0 | 34-21-21 | D00141B | A13 | | | D41351J | 14 | | | ALL |
| 5026Z | | | AZ | | 0-0 | 34-21-21 | D00141B | DED | | | D41351J | | | AZ | ALL |
| 5027B | 22 | GU | BA | | 3-0 | 32-42-11 | D41351J | 29 | | | TB0221Z | 16 | BJ | | 001-099 |
| 5027B | 24 | G2 | BA | | 3-0 | 32-42-11 | TB0221Z | 16 | BJ | | D41351J | 29 | | | 115-199 |
| 5027R | 22 | GU | BA | | 0-0 | 32-42-11 | D41351J | 30 | | | TB0221Z | 15 | BJ | | 001-099 |
| 5027R | 24 | G2 | BA | | 0-0 | 32-42-11 | TB0221Z | 15 | BJ | | D41351J | 30 | | | 115-199 |
| 5027Z | | | BA | | 0-0 | 32-42-11 | D41351J | 31 | | | GD02021 | ST.. | 2 | | 001-099 |
| 5027Z | | | BA | | 0-0 | 32-42-11 | GD02021 | ST.. | 2 | | D41351J | 31 | | | 115-199 |
| 5028B | 24 | G2 | BB | | 4-0 | 34-61-15 | D41569J | 8 | | | TB0221Y | C043 | BJ | | 001-099 |
| 5028B | 24 | G2 | BB | | 4-0 | 34-61-15 | TB0221Y | C043 | BJ | | D41569J | 8 | | | 115-199 |
| 5028R | 24 | G2 | BB | | 0-0 | 34-61-15 | D41569J | 7 | | | TB0221Y | A043 | BJ | | 001-099 |
| 5028R | 24 | G2 | BB | | 0-0 | 34-61-15 | TB0221Y | A043 | BJ | | D41569J | 7 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 160

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1177 | 286N1177 | | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | | |
| 5028Z | | | | BB | 0-0 | 34-61-15 | D41569J | 9 | | | | GD02025 | ST.. | 2 | | 001-099 | |
| 5028Z | | | | BB | 0-0 | 34-61-15 | GD02025 | ST.. | 2 | | | D41569J | 9 | | | 115-199 | |
| 5029B | 24 | G2 | | BC | 3-0 | 34-61-22 | D41351J | 27 | | | | TB0221Z | 16 | BJ | | 001-099 | |
| 5029B | 24 | G2 | | BC | 3-0 | 34-61-22 | TB0221Z | 16 | BJ | | | D41351J | 27 | | | 115-199 | |
| 5029R | 24 | G2 | | BC | 0-0 | 34-61-22 | D41351J | 26 | | | | TB0221Z | 15 | BJ | | 001-099 | |
| 5029R | 24 | G2 | | BC | 0-0 | 34-61-22 | TB0221Z | 15 | BJ | | | D41351J | 26 | | | 115-199 | |
| 5029Z | | | | BC | 0-0 | 34-61-22 | D41351J | 28 | | | | GD02021 | ST.. | 2 | | 001-099 | |
| 5029Z | | | | BC | 0-0 | 34-61-22 | GD02021 | ST.. | 2 | | | D41351J | 28 | | | 115-199 | |
| 5030B | 24 | G2 | | BD | 3-0 | 22-32-11 | D41351J | 24 | | | | TB0221Z | 16 | BJ | | 001-099 | |
| 5030B | 24 | G2 | | BD | 3-0 | 22-32-11 | TB0221Z | 16 | BJ | | | D41351J | 24 | | | 115-199 | |
| 5030R | 24 | G2 | | BD | 0-0 | 22-32-11 | D41351J | 23 | | | | TB0221Z | 15 | BJ | | 001-099 | |
| 5030R | 24 | G2 | | BD | 0-0 | 22-32-11 | TB0221Z | 15 | BJ | | | D41351J | 23 | | | 115-199 | |
| 5030Z | | | | BD | 0-0 | 22-32-11 | D41351J | 25 | | | | GD02021 | ST.. | 2 | | 001-099 | |
| 5030Z | | | | BD | 0-0 | 22-32-11 | GD02021 | ST.. | 2 | | | D41351J | 25 | | | 115-199 | |
| 5031B | 24 | G2 | | BE | 3-0 | 22-21-21 | D41351J | 2 | | | | TB0221Z | 18 | BJ | | 001-099 | |
| 5031B | 24 | G2 | | BE | 3-0 | 22-21-21 | TB0221Z | 18 | BJ | | | D41351J | 2 | | | 115-199 | |
| 5031R | 24 | G2 | | BE | 0-0 | 22-21-21 | D41351J | 1 | | | | TB0221Z | 17 | BJ | | 001-099 | |
| 5031R | 24 | G2 | | BE | 0-0 | 22-21-21 | TB0221Z | 17 | BJ | | | D41351J | 1 | | | 115-199 | |
| 5031Z | | | | BE | 0-0 | 22-21-21 | D41351J | 3 | | | | GD02022 | ST.. | 2 | | 001-099 | |
| 5031Z | | | | BE | 0-0 | 22-21-21 | GD02022 | ST.. | 2 | | | D41351J | 3 | | | 115-199 | |
| 5032B | 24 | G2 | | BF | 3-0 | 34-22-81 | D41351J | 52 | | | | TB0221Z | 16 | BJ | | 001-099 | |
| 5032B | 24 | G2 | | BF | 3-0 | 34-22-83 | TB0221Z | 16 | BJ | | | D41351J | 52 | | | 115-199 | |
| 5032R | 24 | G2 | | BF | 0-0 | 34-22-81 | D41351J | 53 | | | | TB0221Z | 15 | BJ | | 001-099 | |
| 5032R | 24 | G2 | | BF | 0-0 | 34-22-83 | TB0221Z | 15 | BJ | | | D41351J | 53 | | | 115-199 | |
| 5032Z | | | | BF | 0-0 | 34-22-81 | D41351J | 54 | | | | GD02021 | ST.. | 2 | | 001-099 | |
| 5032Z | | | | BF | 0-0 | 34-22-83 | GD02021 | ST.. | 2 | | | D41351J | 54 | | | 115-199 | |
| 5033B | 24 | G2 | | BG | 3-0 | 22-13-21 | D41351J | 21 | | | | TB0221Y | C013 | BJ | | 001-099 | |
| 5033B | 24 | G2 | | BG | 3-0 | 22-13-21 | TB0221Y | C013 | BJ | | | D41351J | 21 | | | 115-199 | |
| 5033R | 24 | G2 | | BG | 0-0 | 22-13-21 | D41351J | 20 | | | | TB0221Y | A013 | BJ | | 001-099 | |
| 5033R | 24 | G2 | | BG | 0-0 | 22-13-21 | TB0221Y | A013 | BJ | | | D41351J | 20 | | | 115-199 | |
| 5033Z | | | | BG | 0-0 | 22-13-21 | D41351J | 22 | | | | GD02021 | ST.. | 2 | | 001-099 | |
| 5033Z | | | | BG | 0-0 | 22-13-21 | GD02021 | ST.. | 2 | | | D41351J | 22 | | | 115-199 | |
| 5034B | 24 | G2 | | BH | 3-0 | 34-22-28 | D41351J | 35 | | | | TB0221Z | 18 | BJ | | 001-099 | |
| 5034B | 24 | G2 | | BH | 3-0 | 34-22-28 | TB0221Z | 18 | BJ | | | D41351J | 35 | | | 115-199 | |
| 5034R | 24 | G2 | | BH | 0-0 | 34-22-28 | D41351J | 34 | | | | TB0221Z | 17 | BJ | | 001-099 | |
| 5034R | 24 | G2 | | BH | 0-0 | 34-22-28 | TB0221Z | 17 | BJ | | | D41351J | 34 | | | 115-199 | |
| 5034Z | | | | BH | 0-0 | 34-22-28 | D41351J | 36 | | | | GD02022 | ST.. | 2 | | 001-099 | |
| 5034Z | | | | BH | 0-0 | 34-22-28 | GD02022 | ST.. | 2 | | | D41351J | 36 | | | 115-199 | |
| 5035B | 24 | G2 | | BI | 3-0 | 34-21-21 | D00141B | G08 | | | | TB0221Z | 18 | BJ | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 161

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1177 | 286N1177 | | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5035R | 24 | G2 | BI | | 0-0 | 34-21-21 | D00141B | G07 | | | TB0221Z | 17 | BJ | | ALL | |
| 5035Z | | | BI | | 0-0 | 34-21-21 | D00141B | DED | | | GD02022 | ST.. | 2 | | ALL | |
| 5036B | 24 | G2 | BJ | | 3-0 | 34-22-92 | D42089J | 4 | | | TB0221Z | 18 | BJ | | 001-099 | |
| 5036B | 24 | G2 | BJ | | 3-0 | 34-22-92 | TB0221Z | 18 | BJ | | D42089J | 4 | | | 115-199 | |
| 5036R | 24 | G2 | BJ | | 0-0 | 34-22-92 | D42089J | 3 | | | TB0221Z | 17 | BJ | | 001-099 | |
| 5036R | 24 | G2 | BJ | | 0-0 | 34-22-92 | TB0221Z | 17 | BJ | | D42089J | 3 | | | 115-199 | |
| 5036Z | | | BJ | | 0-0 | 34-22-92 | D42089J | 5 | | | GD02022 | ST.. | 2 | | 001-099 | |
| 5036Z | | | BJ | | 0-0 | 34-22-92 | GD02022 | ST.. | 2 | | D42089J | 5 | | | 115-199 | |
| 5037B | 24 | G2 | BK | | 3-0 | 34-21-31 | D00139B | J11 | | | TB0221Z | 42 | BJ | | ALL | |
| 5037R | 24 | G2 | BK | | 0-0 | 34-21-31 | D00139B | J10 | | | TB0221Z | 41 | BJ | | ALL | |
| 5037Z | | | BK | | 0-0 | 34-21-31 | D00139B | DED | | | GD02025 | ST.. | 2 | | ALL | |
| 5038B | 24 | G2 | BL | | 2-0 | 34-21-31 | D00139B | C11 | | | TB0221Z | 48 | BJ | | 001-099 | |
| 5038B | 24 | G2 | BL | | 3-0 | 34-21-31 | D00139B | C11 | | | TB0221Z | 48 | BJ | | 115-199 | |
| 5038R | 24 | G2 | BL | | 0-0 | 34-21-31 | D00139B | C10 | | | TB0221Z | 47 | BJ | | ALL | |
| 5038Z | | | BL | | 0-0 | 34-21-31 | D00139B | DED | | | GD02026 | ST.. | 2 | | ALL | |
| 5039B | 24 | G2 | BM | | 3-0 | 34-21-31 | D42205J | 14 | | | TB0221Z | 48 | BJ | | 001-099 | |
| 5039B | 24 | G2 | BM | | 3-0 | 34-21-31 | TB0221Z | 48 | BJ | | D42205J | 14 | | | 115-199 | |
| 5039R | 24 | G2 | BM | | 0-0 | 34-21-31 | D42205J | 13 | | | TB0221Z | 47 | BJ | | 001-099 | |
| 5039R | 24 | G2 | BM | | 0-0 | 34-21-31 | TB0221Z | 47 | BJ | | D42205J | 13 | | | 115-199 | |
| 5039Z | | | BM | | 0-0 | 34-21-31 | D42205J | 15 | | | GD02026 | ST.. | 2 | | 001-099 | |
| 5039Z | | | BM | | 0-0 | 34-21-31 | GD02026 | ST.. | 2 | | D42205J | 15 | | | 115-199 | |
| 5040B | 24 | G2 | BN | | 3-0 | 34-21-31 | D00139B | C06 | | | D42205J | 11 | | | ALL | |
| 5040R | 24 | G2 | BN | | 0-0 | 34-21-31 | D00139B | C05 | | | D42205J | 10 | | | ALL | |
| 5040Z | | | BN | | 0-0 | 34-21-31 | D00139B | DED | | | D42205J | | | BN | ALL | |
| 5041B | 24 | G2 | BO | | 3-0 | 34-21-31 | D00139B | A14 | | | TB0221Y | C014 | BJ | | ALL | |
| 5041R | 24 | G2 | BO | | 0-0 | 34-21-31 | D00139B | A13 | | | TB0221Y | A014 | BJ | | ALL | |
| 5041Z | | | BO | | 0-0 | 34-21-31 | D00139B | DED | | | GD02021 | ST.. | 2 | | ALL | |
| 5042B | 24 | G2 | BP | | 2-0 | 34-21-31 | D00139B | K05 | | | TB0221Y | C045 | BJ | | ALL | |
| 5042R | 24 | G2 | BP | | 0-0 | 34-21-31 | D00139B | K04 | | | TB0221Y | A045 | BJ | | ALL | |
| 5042Z | | | BP | | 0-0 | 34-21-31 | D00139B | DED | | | GD02025 | ST.. | 2 | | ALL | |
| 5043B | 24 | G2 | BQ | | 2-0 | 34-21-31 | D00139B | A09 | | | TB0221Y | C043 | BJ | | ALL | |
| 5043R | 24 | G2 | BQ | | 0-0 | 34-21-31 | D00139B | A08 | | | TB0221Y | A043 | BJ | | ALL | |
| 5043Z | | | BQ | | 0-0 | 34-21-31 | D00139B | DED | | | GD02025 | ST.. | 2 | | ALL | |
| 5044B | 24 | G2 | BR | | 2-0 | 34-21-31 | D00139B | G08 | | | TB0221Y | C049 | BJ | | ALL | |
| 5044R | 24 | G2 | BR | | 0-0 | 34-21-31 | D00139B | G07 | | | TB0221Y | A049 | BJ | | ALL | |
| 5044Z | | | BR | | 0-0 | 34-21-31 | D00139B | DED | | | GD02026 | ST.. | 2 | | ALL | |
| 5045B | 24 | G2 | BS | | 3-0 | 34-22-38 | D41397J | 18 | | | TB0221Y | C044 | BJ | | 001-099 | |
| 5045B | 24 | G2 | BS | | 3-0 | 34-22-38 | TB0221Y | C044 | BJ | | D41397J | 18 | | | 115-199 | |
| 5045R | 24 | G2 | BS | | 0-0 | 34-22-38 | D41397J | 17 | | | TB0221Y | A044 | BJ | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 162

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1177 | 286N1177 | | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | |
| 5045R | 24 | | G2 | BS | 0-0 | 34-22-38 | TB0221Y | A044 | BJ | | D41397J | 17 | | | 115-199 |
| 5045Z | | | | BS | 0-0 | 34-22-38 | D41397J | 19 | | | GD02025 | ST.. | 2 | | 001-099 |
| 5045Z | | | | BS | 0-0 | 34-22-38 | GD02025 | ST.. | 2 | | D41397J | 19 | | | 115-199 |
| 5046B | 24 | | G2 | BT | 3-0 | 34-22-18 | D41397J | 5 | | | TB0221Y | C049 | BJ | | 001-099 |
| 5046B | 24 | | G2 | BT | 3-0 | 34-22-18 | TB0221Y | C049 | BJ | | D41397J | 5 | | | 115-199 |
| 5046R | 24 | | G2 | BT | 0-0 | 34-22-18 | D41397J | 4 | | | TB0221Y | A049 | BJ | | 001-099 |
| 5046R | 24 | | G2 | BT | 0-0 | 34-22-18 | TB0221Y | A049 | BJ | | D41397J | 4 | | | 115-199 |
| 5046Z | | | | BT | 0-0 | 34-22-18 | D41397J | 6 | | | GD02026 | ST.. | 2 | | 001-099 |
| 5046Z | | | | BT | 0-0 | 34-22-18 | GD02026 | ST.. | 2 | | D41397J | 6 | | | 115-199 |
| 5047B | 24 | | G2 | BU | 3-0 | 34-21-31 | D00139B | E06 | | | TB0221Y | C044 | BJ | | ALL |
| 5047R | 24 | | G2 | BU | 0-0 | 34-21-31 | D00139B | E05 | | | TB0221Y | A044 | BJ | | ALL |
| 5047Z | | | | BU | 0-0 | 34-21-31 | D00139B | DED | | | GD02025 | ST.. | 2 | | ALL |
| 5048B | 24 | | G2 | BV | 3-0 | 34-22-28 | D41397J | 2 | | | TB0221Y | C049 | BJ | | 001-099 |
| 5048B | 24 | | G2 | BV | 3-0 | 34-22-28 | TB0221Y | C049 | BJ | | D41397J | 2 | | | 115-199 |
| 5048R | 24 | | G2 | BV | 0-0 | 34-22-28 | D41397J | 1 | | | TB0221Y | A049 | BJ | | 001-099 |
| 5048R | 24 | | G2 | BV | 0-0 | 34-22-28 | TB0221Y | A049 | BJ | | D41397J | 1 | | | 115-199 |
| 5048Z | | | | BV | 0-0 | 34-22-28 | D41397J | 3 | | | GD02026 | ST.. | 2 | | 001-099 |
| 5048Z | | | | BV | 0-0 | 34-22-28 | GD02026 | ST.. | 2 | | D41397J | 3 | | | 115-199 |
| 5049B | 24 | | G2 | BW | 3-0 | 34-61-12 | D41351J | 18 | | | TB0221Z | 48 | BJ | | 001-099 |
| 5049B | 24 | | G2 | BW | 3-0 | 34-61-12 | TB0221Z | 48 | BJ | | D41351J | 18 | | | 115-199 |
| 5049R | 24 | | G2 | BW | 0-0 | 34-61-12 | D41351J | 17 | | | TB0221Z | 47 | BJ | | 001-099 |
| 5049R | 24 | | G2 | BW | 0-0 | 34-61-12 | TB0221Z | 47 | BJ | | D41351J | 17 | | | 115-199 |
| 5049Z | | | | BW | 0-0 | 34-61-12 | D41351J | 19 | | | GD02026 | ST.. | 2 | | 001-099 |
| 5049Z | | | | BW | 0-0 | 34-61-12 | GD02026 | ST.. | 2 | | D41351J | 19 | | | 115-199 |
| 5050B | 24 | | G2 | BX | 3-0 | 22-21-11 | D41397J | 14 | | | TB0221Z | 48 | BJ | | 001-099 |
| 5050B | 24 | | G2 | BX | 3-0 | 22-21-11 | TB0221Z | 48 | BJ | | D41397J | 14 | | | 115-199 |
| 5050R | 24 | | G2 | BX | 0-0 | 22-21-11 | D41397J | 13 | | | TB0221Z | 47 | BJ | | 001-099 |
| 5050R | 24 | | G2 | BX | 0-0 | 22-21-11 | TB0221Z | 47 | BJ | | D41397J | 13 | | | 115-199 |
| 5050Z | | | | BX | 0-0 | 22-21-11 | D41397J | 15 | | | GD02026 | ST.. | 2 | | 001-099 |
| 5050Z | | | | BX | 0-0 | 22-21-11 | GD02026 | ST.. | 2 | | D41397J | 15 | | | 115-199 |
| 5051B | 24 | | G2 | BY | 3-0 | 34-22-81 | D42051J | 5 | | | TB0221Z | 48 | BJ | | 001-099 |
| 5051B | 24 | | G2 | BY | 3-0 | 34-22-83 | TB0221Z | 48 | BJ | | D42051J | 15 | | | 115-199 |
| 5051R | 24 | | G2 | BY | 0-0 | 34-22-81 | D42051J | 6 | | | TB0221Z | 47 | BJ | | 001-099 |
| 5051R | 24 | | G2 | BY | 0-0 | 34-22-83 | TB0221Z | 47 | BJ | | D42051J | 16 | | | 115-199 |
| 5051Z | | | | BY | 0-0 | 34-22-81 | D42051J | 7 | | | GD02026 | ST.. | 2 | | 001-099 |
| 5051Z | | | | BY | 0-0 | 34-22-83 | GD02026 | ST.. | 2 | | D42051J | 17 | | | 115-199 |
| 5052B | 24 | | G2 | BZ | 3-0 | 34-22-82 | D42051J | 9 | | | TB0221Y | C044 | BJ | | 001-099 |
| 5052B | 24 | | G2 | BZ | 3-0 | 34-22-82 | TB0221Y | C044 | BJ | | D42051J | 29 | | | 115-199 |
| 5052R | 24 | | G2 | BZ | 0-0 | 34-22-82 | D42051J | 8 | | | TB0221Y | A044 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 163

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1177 | 286N1177 | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5052R | 24 | | G2 | BZ | 0-0 | 34-22-82 | TB0221Y | A044 | BJ | | D42051J | 28 | | | 115-199 |
| 5052Z | | | | BZ | 0-0 | 34-22-82 | D42051J | 10 | | | GD02025 | ST.. | 2 | | 001-099 |
| 5052Z | | | | BZ | 0-0 | 34-22-82 | GD02025 | ST.. | 2 | | D42051J | 30 | | | 115-199 |
| 5054B | 22 | | GU | CB | 4-0 | 32-42-11 | D41397J | 21 | | | TB0221Z | 48 | BJ | | 001-099 |
| 5054B | 24 | | G2 | CB | 4-0 | 32-42-11 | TB0221Z | 48 | BJ | | D41397J | 21 | | | 115-199 |
| 5054R | 22 | | GU | CB | 0-0 | 32-42-11 | D41397J | 22 | | | TB0221Z | 47 | BJ | | 001-099 |
| 5054R | 24 | | G2 | CB | 0-0 | 32-42-11 | TB0221Z | 47 | BJ | | D41397J | 22 | | | 115-199 |
| 5054Z | | | | CB | 0-0 | 32-42-11 | D41397J | 23 | | | GD02026 | ST.. | 2 | | 001-099 |
| 5054Z | | | | CB | 0-0 | 32-42-11 | GD02026 | ST.. | 2 | | D41397J | 23 | | | 115-199 |
| 5055B | 24 | | G2 | CC | 3-0 | 34-21-11 | D00137B | E06 | | | TB0221Y | C084 | BJ | | ALL |
| 5055R | 24 | | G2 | CC | 0-0 | 34-21-11 | D00137B | E05 | | | TB0221Y | A084 | BJ | | ALL |
| 5055Z | | | | CC | 0-0 | 34-21-11 | D00137B | DED | | | GD02030 | ST.. | 2 | | 001-099 |
| 5055Z | | | | CC | 0-0 | 34-21-11 | D00137B | DED | | | GD02029 | ST.. | 2 | | 115-199 |
| 5056B | 24 | | G2 | CD | 3-0 | 22-21-21 | D41099J | 5 | | | TB0221Y | C084 | BJ | | 001-099 |
| 5056B | 24 | | G2 | CD | 3-0 | 22-21-21 | TB0221Y | C084 | BJ | | D41099J | 5 | | | 115-199 |
| 5056R | 24 | | G2 | CD | 0-0 | 22-21-21 | D41099J | 6 | | | TB0221Y | A084 | BJ | | 001-099 |
| 5056R | 24 | | G2 | CD | 0-0 | 22-21-21 | TB0221Y | A084 | BJ | | D41099J | 6 | | | 115-199 |
| 5056Z | | | | CD | 0-0 | 22-21-21 | D41099J | 7 | | | GD02030 | ST.. | 2 | | 001-099 |
| 5056Z | | | | CD | 0-0 | 22-21-21 | GD02030 | ST.. | 2 | | D41099J | 7 | | | 115-199 |
| 5057B | 24 | | G2 | CE | 5-0 | 34-22-38 | D41001J | 11 | | | TB0221Z | 18 | BJ | | 001-099 |
| 5057B | 24 | | G2 | CE | 5-0 | 34-22-38 | TB0221Z | 18 | BJ | | D41001J | 11 | | | 115-199 |
| 5057R | 24 | | G2 | CE | 0-0 | 34-22-38 | D41001J | 10 | | | TB0221Z | 17 | BJ | | 001-099 |
| 5057R | 24 | | G2 | CE | 0-0 | 34-22-38 | TB0221Z | 17 | BJ | | D41001J | 10 | | | 115-199 |
| 5057Z | | | | CE | 0-0 | 34-22-38 | D41001J | 12 | | | GD02022 | ST.. | 2 | | 001-099 |
| 5057Z | | | | CE | 0-0 | 34-22-38 | GD02022 | ST.. | 2 | | D41001J | 12 | | | 115-199 |
| 5058B | 24 | | G2 | CF | 4-0 | 34-21-11 | D41099J | 38 | | | TB0221Y | C045 | BJ | | 001-099 |
| 5058B | 24 | | G2 | CF | 4-0 | 34-21-11 | TB0221Y | C045 | BJ | | D41099J | 38 | | | 115-199 |
| 5058R | 24 | | G2 | CF | 0-0 | 34-21-11 | D41099J | 37 | | | TB0221Y | A045 | BJ | | 001-099 |
| 5058R | 24 | | G2 | CF | 0-0 | 34-21-11 | TB0221Y | A045 | BJ | | D41099J | 37 | | | 115-199 |
| 5058Z | | | | CF | 0-0 | 34-21-11 | D41099J | 39 | | | GD02025 | ST.. | 2 | | 001-099 |
| 5058Z | | | | CF | 0-0 | 34-21-11 | GD02025 | ST.. | 2 | | D41099J | 39 | | | 115-199 |
| 5059B | 24 | | G2 | CG | 3-0 | 22-21-11 | D41351J | 42 | | | TB0221Y | C013 | BJ | | 001-099 |
| 5059B | 24 | | G2 | CG | 3-0 | 22-21-11 | TB0221Y | C013 | BJ | | D41351J | 42 | | | 115-199 |
| 5059R | 24 | | G2 | CG | 0-0 | 22-21-11 | D41351J | 41 | | | TB0221Y | A013 | BJ | | 001-099 |
| 5059R | 24 | | G2 | CG | 0-0 | 22-21-11 | TB0221Y | A013 | BJ | | D41351J | 41 | | | 115-199 |
| 5059Z | | | | CG | 0-0 | 22-21-11 | D41351J | 43 | | | GD02021 | ST.. | 2 | | 001-099 |
| 5059Z | | | | CG | 0-0 | 22-21-11 | GD02021 | ST.. | 2 | | D41351J | 43 | | | 115-199 |
| 5060B | 24 | | G2 | CH | 3-0 | 34-21-21 | D00141B | E06 | | | TB0221Y | C013 | BJ | | ALL |
| 5060R | 24 | | G2 | CH | 0-0 | 34-21-21 | D00141B | E05 | | | TB0221Y | A013 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 164

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1177 | 286N1177 | | | E2-4 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5060Z | | | | CH | 0-0 | 34-21-21 | D00141B | DED | | | GD02021 | ST.. | 2 | | ALL |
| 5065B | 22 | GU | CI | | 3-8 | 34-58-11 | D41099J | 40 | | | TB0221Y | C084 | BJ | | 115-199 |
| 5065R | 22 | GU | CI | | 0-0 | 34-58-11 | D41099J | 36 | | | TB0221Y | A084 | BJ | | 115-199 |
| 5065Z | | | | CI | 0-0 | 34-58-11 | D41099J | 41 | | | GD02030 | ST.. | 2 | | 115-199 |
| 5072B | 22 | GU | CJ | | 3-8 | 34-58-11 | D41397J | 54 | | | TB0221Y | C049 | BJ | | 115-199 |
| 5072R | 22 | GU | CJ | | 0-0 | 34-58-11 | D41397J | 53 | | | TB0221Y | A049 | BJ | | 115-199 |
| 5072Z | | | | CJ | 0-0 | 34-58-11 | D41397J | 55 | | | GD02026 | ST.. | 2 | | 115-199 |
| 5074B | 22 | GU | CK | | 3-8 | 34-58-21 | D41397J | 51 | | | TB0221Z | 48 | BJ | | 115-199 |
| 5074R | 22 | GU | CK | | 0-0 | 34-58-21 | D41397J | 50 | | | TB0221Z | 47 | BJ | | 115-199 |
| 5074Z | | | | CK | 0-0 | 34-58-21 | D41397J | 52 | | | GD02026 | ST.. | 2 | | 115-199 |
| 5082B | 22 | GU | CA | | 3-2 | 34-58-21 | D41001J | 5 | | | TB0221Y | C013 | BJ | | 115-199 |
| 5082R | 22 | GU | CA | | 0-0 | 34-58-21 | D41001J | 4 | | | TB0221Y | A013 | BJ | | 115-199 |
| 5082Z | | | | CA | 0-0 | 34-58-21 | D41001J | 6 | | | GD02021 | ST.. | 2 | | 115-199 |
| 5096B | 22 | GU | CT | | 3-0 | 34-46-12 | D41351J | 45 | | | TB0221Z | 16 | BJ | | 002 |
| 5096R | 22 | GU | CT | | 0-0 | 34-46-12 | D41351J | 44 | | | TB0221Z | 15 | BJ | | 002 |
| 5096Z | | | | CT | 0-0 | 34-46-12 | D41351J | 46 | | | GD02022 | ST.. | 2 | | 002 |
| FRAB | | | | | 0-0 | 34-21-11 | D42201J | | | AB | D42201J | 12 | | | ALL |
| FRAI | | | | | 0-0 | 34-21-11 | D41569J | | | AI | D41569J | 15 | | | ALL |
| FRAS | | | | | 0-0 | 34-21-21 | D41001J | | | AS | D41001J | 3 | | | ALL |
| FRAT | | | | | 0-0 | 34-21-21 | D42203J | | | AT | D42203J | 12 | | | ALL |
| FRAZ | | | | | 0-0 | 34-21-21 | D41351J | | | AZ | D41351J | 16 | | | ALL |
| FRBG | | | | | 0-0 | 34-21-21 | D41351J | | | BG | D41351J | 13 | | | ALL |
| FRBN | | | | | 0-0 | 34-21-31 | D42205J | | | BN | D42205J | 12 | | | ALL |
| W1179 | 286N1179 | | | E2-4 SHELF BUNDLE (S1) | | | | | | | | | | | |
| 0001 | 20 | GA | | | 2-1 | 34-21-11 | D00137C | 5 | | | GD02030 | AC.. | 2 | | 115-199 |
| 0002 | 14 | GA | | | 1-11 | 34-21-11 | D00137C | 8 | | | GD02031 | DC.. | E | | 115-199 |
| 0003 | 16 | GA | | | 2-1 | 34-21-11 | D00137C | 11 | | | GD02030 | ST.. | 2 | | 115-199 |
| 0004 | 14 | GA | | | 4-3 | 34-21-11 | D00137C | 7 | | | D42225J | 1 | | | 115-199 |
| 0005 | 24 | GK | | | 2-9 | 34-21-11 | D00137C | 1 | | | D41758J | 2 | | | 115-199 |
| 0006 | 14 | GA | | | 1-11 | 34-21-21 | D00141C | 8 | | | GD02023 | DC.. | E | | 115-199 |
| 0007 | 14 | GA | | | 3-7 | 34-21-21 | D00141C | 7 | | | D42227J | 2 | | | 115-199 |
| 0008 | 16 | GA | | | 2-0 | 34-21-21 | D00141C | 11 | | | GD02020 | ST.. | 2 | | 115-199 |
| 0009 | 20 | GA | | | 2-0 | 34-21-21 | D00141C | 5 | | | GD02020 | AC.. | 2 | | 115-199 |
| 0010 | 24 | GK | | | 2-4 | 34-21-21 | D00141C | 1 | | | D41916J | 8 | | | 115-199 |
| 0011 | 14 | GA | | | 2-10 | 34-21-31 | D00139C | 8 | | | GD02027 | DC.. | E | | 115-199 |
| 0012 | 14 | GA | | | 2-6 | 34-21-31 | D00139C | 7 | | | D42229J | 3 | | | 115-199 |
| 0013 | 16 | GA | | | 2-11 | 34-21-31 | D00139C | 11 | | | GD02020 | ST.. | 2 | | 115-199 |
| 0014 | 20 | GA | | | 2-11 | 34-21-31 | D00139C | 5 | | | GD02020 | AC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 165

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1179 | 286N1179 | | | E2-4 SHELF BUNDLE (S1) (continued) | | | | | | | | | | | |
| 0015 | 24 | | GK | | 2-1 | 34-21-31 | D00139C | | 1 | | TB0221Y | A039 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1170

Page 166 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|------------------------------------|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1190 | 286N1190 | P34 CB PANEL-INTERNALWIRING | | | | | | | | | | | | | |
| 0001 | 14 | GA | | | 6-0 | 24-51-61 | C00304 | A1 | D | * | K00101 | A2 | F | | 001-099 |
| 0001 | 14 | GA | | | 6-0 | 24-51-61 | C00304 | A1 | D | * | C00309 | A2 | D | | 115-199 |
| 0002 | 14 | GA | | | 6-0 | 24-51-61 | C00304 | B1 | D | * | K00101 | B2 | F | | 001-099 |
| 0002 | 14 | GA | | | 6-0 | 24-51-61 | C00304 | B1 | D | * | C00309 | B2 | D | | 115-199 |
| 0003 | 14 | GA | | | 6-0 | 24-51-61 | C00304 | C1 | D | * | K00101 | C2 | F | | 001-099 |
| 0003 | 14 | GA | | | 6-0 | 24-51-61 | C00304 | C1 | D | * | C00309 | C2 | D | | 115-199 |
| 0004 | 14 | GA | | | 2-0 | 24-51-61 | C00304 | A1 | D | * | C00360 | A2 | D | * | ALL |
| 0005 | 14 | GA | | | 2-0 | 24-51-61 | C00304 | B1 | D | * | C00360 | B2 | D | * | ALL |
| 0006 | 14 | GA | | | 2-0 | 24-51-61 | C00304 | C1 | D | * | C00360 | C2 | D | * | ALL |
| 0007 | 14 | GA | | | 1-0 | 24-51-61 | C00360 | A2 | D | * | C00361 | A2 | D | | 001-099 |
| 0007 | 14 | GA | | | 1-0 | 24-51-61 | C00360 | A2 | D | * | C00361 | A2 | D | * | 115-199 |
| 0008 | 14 | GA | | | 1-0 | 24-51-61 | C00360 | B2 | D | * | C00361 | B2 | D | | 001-099 |
| 0008 | 14 | GA | | | 1-0 | 24-51-61 | C00360 | B2 | D | * | C00361 | B2 | D | * | 115-199 |
| 0009 | 14 | GA | | | 1-0 | 24-51-61 | C00360 | C2 | D | * | C00361 | C2 | D | | 001-099 |
| 0009 | 14 | GA | | | 1-0 | 24-51-61 | C00360 | C2 | D | * | C00361 | C2 | D | * | 115-199 |
| 0010 | 14 | GA | | | 3-0 | 24-51-61 | C00361 | A2 | D | * | C03018 | A1 | D | | 115-199 |
| 0011 | 14 | GA | | | 3-0 | 24-51-61 | C00361 | B2 | D | * | C03018 | B1 | D | | 115-199 |
| 0012 | 14 | GA | | | 3-0 | 24-51-61 | C00361 | C2 | D | * | C03018 | C1 | D | | 115-199 |
| 0017 | 14 | GA | | | 2-0 | 24-51-61 | C01206 | =B | D | | C00304 | A1 | D | * | ALL |
| 0018 | 14 | GA | | | 4-0 | 24-54-61 | C01041 | =B | D | | C01300 | =B | D | * | 001-099 |
| 0018 | 14 | GA | | | 4-0 | 24-54-61 | C01041 | =B | D | | C01300 | =B | D | | 115-199 |
| 0020 | 14 | GA | | | 2-0 | 24-51-61 | C01210 | =B | D | | C00304 | C1 | D | * | ALL |
| 0021 | 14 | GA | | | 2-0 | 24-51-61 | C01215 | =B | D | | C00304 | B1 | D | * | ALL |
| 0022 | 16 | GA | | | 13-0 | 33-21-31 | C04211 | =L | D | | TB0047G | 2 | 2 | | 001-099 |
| 0022 | 16 | GA | | | 11-0 | 33-21-31 | C04211 | =L | D | | TB0047G | 27 | 2 | | 115-199 |
| 0023 | 16 | GA | | | 13-0 | 33-21-31 | C01266 | =L | D | | TB0047F | A025 | 2 | | 001-099 |
| 0023 | 16 | GA | | | 11-0 | 33-21-31 | C01266 | =L | D | | TB0047F | A025 | 2 | | 115-199 |
| 0025 | 14 | GA | | | 2-0 | 24-51-61 | C01266 | =B | D | * | C01256 | =B | D | | ALL |
| 0026 | 14 | GA | | | 2-0 | 24-51-61 | C04211 | =B | D | | C01266 | =B | D | * | ALL |
| 0027 | 14 | GA | | | 1-0 | 24-54-61 | C01403 | =B | D | | C01047 | =B | D | | 001-099 |
| 0028 | 14 | GA | | | 4-0 | 24-54-61 | C01300 | =B | D | * | C04291 | =B | D | | 001-099 |
| 0028 | 14 | GA | | | 4-0 | 24-54-61 | C01300 | =B | D | | C04291 | =B | D | | 115-199 |
| 0100 | 24 | GK | | | 9-0 | 24-34-11 | D40956J | 26 | | | C04291 | =L | D | | 001-099 |
| 0100 | 22 | GA | | | 9-0 | 24-34-11 | D40956J | 26 | | | C04291 | =L | D | | 115-199 |
| 0101 | 20 | GA | | | 7-0 | 52-34-11 | C00360 | A1 | D | | D40080J | 1 | | | ALL |
| 0102 | 20 | GA | | | 7-0 | 52-34-11 | C00360 | B1 | D | | D40080J | 2 | | | ALL |
| 0103 | 20 | GA | | | 7-0 | 52-34-11 | C00360 | C1 | D | | D40080J | 3 | | | ALL |
| 0104 | 22 | GA | | | 8-0 | 33-37-11 | C01211 | =L | D | | D40080J | 5 | | | 001-099 |
| 0104 | 20 | GA | | | 8-0 | 33-37-11 | C01211 | =L | D | | D40080J | 5 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1190

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1190 | 286N1190 | | | P34 CB PANEL-INTERNALWIRING (continued) | | | | | | | | | | | |
| 0105 | 22 | GA | | | 8-0 | 52-34-11 | C01403 | =L | D | | D40080J | 4 | | | ALL |
| 0106 | 22 | GA | | | 8-0 | 25-51-11 | C04180 | =L | + | | D40080J | 6 | | | 115-199 |
| 0107 | 18 | GA | | | 9-0 | 25-51-11 | C03018 | CAP | Y | | D40080J | 7 | | | 115-199 |
| 0108 | 18 | GA | | | 9-0 | 25-51-11 | C03018 | CAP | Y | | D40080J | 8 | | | 115-199 |
| 0109 | 18 | GA | | | 9-0 | 25-51-11 | C03018 | CAP | Y | | D40080J | 9 | | | 115-199 |
| 0201 | 20 | GA | | | 7-0 | 52-35-11 | C00361 | A1 | D | | D40188J | 4 | | | ALL |
| 0202 | 20 | GA | | | 7-0 | 52-35-11 | C00361 | B1 | D | | D40188J | 7 | | | ALL |
| 0203 | 20 | GA | | | 7-0 | 52-35-11 | C00361 | C1 | D | | D40188J | 10 | | | ALL |
| 0204 | 20 | GA | | | 8-0 | 33-37-21 | C01210 | =L | D | | D40188J | 1 | | | ALL |
| 0205 | 22 | GA | | | 8-0 | 25-51-21 | C04180 | =L | D | | D40188J | 5 | | | 115-199 |
| 0206 | 18 | GA | | | 9-0 | 25-51-21 | C03018 | A2 | D | | D40188J | 6 | | | 115-199 |
| 0207 | 18 | GA | | | 9-0 | 25-51-21 | C03018 | B2 | D | | D40188J | 3 | | | 115-199 |
| 0208 | 18 | GA | | | 9-0 | 25-51-21 | C03018 | C2 | D | | D40188J | 8 | | | 115-199 |
| 0301 | 22 | GA | | | 9-0 | 33-31-11 | C01206 | =L | D | | D41326J | 24 | | | 001-099 |
| 0301 | 20 | GA | | | 9-0 | 33-31-11 | C01206 | =L | D | | D41326J | 24 | | | 115-199 |
| 0302 | 22 | GA | | | 8-0 | 33-31-31 | C01256 | =L | D | | D40400J | 14 | | | ALL |
| 0303 | 18 | GA | | | 8-0 | 33-31-21 | C01300 | =L | D | | D40188J | 14 | | | ALL |
| 0304 | 22 | GA | | | 9-0 | 33-26-11 | C01215 | =L | D | | D41326J | 25 | | | ALL |
| 0305 | 24 | GK | | | 9-0 | 38-32-21 | C04086 | =L | D | | D41326J | 3 | | | 001-099 |
| 0305 | 20 | GA | | | 9-0 | 38-32-21 | C04086 | =L | D | | D41326J | 3 | | | 115-199 |
| 0306 | 22 | GA | | | 12-0 | 38-14-11 | C01356 | =L | D | | TB0047Z | 16 | BJ | | 001-099 |
| 0306 | 22 | GA | | | 11-0 | 38-14-11 | C01356 | =L | D | | TB0047Y | C017 | BJ | | 115-199 |
| 0401 | 16 | GA | | | 12-0 | 28-21-11 | C01047 | =L | D | | TB0047F | C019 | 2 | | 001-099 |
| 0401 | 16 | GA | | | 11-0 | 28-21-11 | C01047 | =L | D | | TB0047F | C019 | 2 | | 115-199 |
| 0402 | 16 | GA | | | 12-0 | 28-21-11 | C01040 | =L | D | | TB0047F | A019 | 2 | | 001-099 |
| 0402 | 16 | GA | | | 11-0 | 28-21-11 | C01040 | =L | D | | TB0047F | A019 | 2 | | 115-199 |
| 0403 | 16 | GA | | | 12-0 | 28-21-11 | C01041 | =L | D | | TB0047F | A024 | 2 | | 001-099 |
| 0403 | 16 | GA | | | 11-0 | 28-21-11 | C01041 | =L | D | | TB0047F | A024 | 2 | | 115-199 |
| ZZAA | 03 | ZB | | | 0-0 | 24-54-61 | C01403 | =B | D | | C04086 | =B | D | | 001-099 |
| ZZAB | 02 | ZB | | | 0-0 | 24-51-61 | C01211 | =B | D | | C01210 | =B | D | | ALL |
| ZZAF | 03 | ZB | | | 0-0 | 24-54-61 | C01047 | =B | D | | C01041 | =B | D | | 001-099 |
| ZZAF | 09 | ZB | | | 0-0 | 24-54-61 | C04086 | =B | D | | C01041 | =B | D | | 115-199 |
| ZZAG | 00 | ZB | | | 0-0 | 24-54-61 | C01041 | =B | D | | C01040 | =B | D | | ALL |
| ZZAH | 00 | ZB | | | 0-0 | 24-54-61 | C01040 | =B | D | | C01047 | =B | D | | ALL |
| ZZAI | 00 | ZB | | | 0-0 | 24-54-61 | C01047 | =B | D | | C04180 | =B | D | | 115-199 |
| ZZAK | 00 | ZB | | | 0-0 | 24-54-61 | C04180 | =B | D | | C01403 | =B | D | | 115-199 |
| ZZAM | 00 | ZB | | | 0-0 | 24-54-61 | C01403 | =B | D | | C01356 | =B | D | | ALL |
| ZZAN | 00 | ZB | | | 0-0 | 24-54-61 | C01356 | =B | D | | C04086 | =B | D | | ALL |
| ZZXB | 02 | ZA | | | 0-0 | 24-51-61 | C01206 | =B | D | | C01256 | =B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1190

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1190 | 286N1190 | | | | P34 CB PANEL-INTERNAL WIRING (continued) | | | | | | | | | | |
| ZZXB | 02 | | ZA | | 0-5 | 24-51-61 | C01206 | =B | D | | C01256 | =B | D | | 115-199 |
| W1196 | 286N1196 | | | | P34 CB SIDE PANEL INTERNAL WIRING | | | | | | | | | | |
| 0001 | 10 | | HA | | 1-1 | 24-53-51 | C01203 | =B | D | * | C01213 | =B | D | | 001-099 |
| 0001 | 10 | | HA | | 1-2 | 24-53-51 | C01203 | =B | D | * | C01213 | =B | D | | 115-199 |
| 0002 | 10 | | HA | | 1-4 | 24-53-51 | C01269 | =B | D | | C04219 | =B | D | | 001-099 |
| 0002 | 10 | | HA | | 1-0 | 24-53-51 | C01269 | =B | D | | C04219 | =B | D | | 115-199 |
| 0003 | 10 | | HA | | 0-11 | 24-53-51 | C01253 | =B | D | | C04218 | =B | D | * | 001-099 |
| 0003 | 10 | | HA | | 1-0 | 24-53-51 | C01253 | =B | D | | C04218 | =B | D | * | 115-199 |
| 0004 | 10 | | HA | | 1-2 | 24-53-51 | C01296 | =B | D | | C01270 | =B | D | | 001-099 |
| 0004 | 10 | | HA | | 1-0 | 24-53-51 | C01296 | =B | D | | C01270 | =B | D | | 115-199 |
| 0005 | 10 | | HA | | 0-11 | 24-53-51 | C04095 | =B | D | | C04146 | =B | D | | ALL |
| 0006 | 06 | | CQ | | 3-0 | 24-53-51 | C04218 | =B | D | * | T00126 | LV | E | | 001-099 |
| 0006 | 08 | | HA | | 2-8 | 24-53-51 | C04218 | =B | D | * | TB5034 | 1 | E | | 115-199 |
| 0007 | 20 | | GA | | 4-0 | 33-22-11 | C01269 | =L | D | | TB0047Z | 7 | BJ | | 001-099 |
| 0007 | 20 | | GA | | 5-0 | 33-22-11 | C01269 | =L | D | | TB0047Z | 7 | BJ | | 115-199 |
| 0008 | 22 | | GA | | 4-0 | 33-24-11 | C04219 | =L | D | | TB0047Y | A013 | BJ | | 001-099 |
| 0008 | 22 | | GA | | 5-0 | 33-24-11 | C04219 | =L | D | | TB0047Y | A013 | BJ | | 115-199 |
| 0009 | 22 | | GA | | 4-0 | 33-24-11 | C01253 | =L | D | | TB0047Y | C013 | BJ | | 001-099 |
| 0009 | 22 | | GA | | 5-0 | 33-24-11 | C01253 | =L | D | | TB0047Y | C013 | BJ | | 115-199 |
| 0010 | 18 | | GA | | 4-0 | 33-24-11 | C01296 | =L | D | | TB0047F | A001 | 2 | | 001-099 |
| 0010 | 20 | | GA | | 5-0 | 33-24-11 | C01296 | =L | D | | TB0047Y | C011 | BJ | | 115-199 |
| 0011 | 18 | | GA | | 4-0 | 33-24-11 | C04218 | =L | D | | TB0047F | C001 | 2 | | 001-099 |
| 0011 | 20 | | GA | | 5-0 | 33-24-11 | C04218 | =L | D | | TB0047X | B006 | BJ | | 115-199 |
| 0013 | 12 | | HA | | 3-8 | 24-54-61 | TB5034 | | 3 | E | C04220 | =B | D | | 115-199 |
| 0014 | 22 | | GA | | 4-0 | 35-11-13 | C04220 | =L | D | | D41472J | 40 | | | 115-199 |
| 0015 | 12 | | HA | | 2-11 | 24-54-61 | C01205 | =B | D | | TB5034 | 3 | E | | 001-099 |
| 0015 | 12 | | HA | | 1-10 | 24-54-61 | C01205 | =B | D | | C04220 | =B | D | | 115-199 |
| 0016 | 20 | | GA | | 5-0 | 30-71-11 | C04367 | =L | D | | D41470J | 24 | | | ALL |
| 0017 | 06 | | CQ | | 0-8 | 24-53-51 | T00126 | GND | E | | GD03014 | AC.. | F | | 001-099 |
| 0018 | 16 | | GA | | 5-0 | 33-26-11 | C04360 | =L | D | | D41472J | 15 | 16 | | 001-099 |
| 0018 | 22 | | GA | | 5-0 | 33-26-11 | C04360 | CAP | Y | | D41472J | 15 | | | 115-199 |
| 0019 | 18 | | GA | | 5-0 | 24-51-25 | C04359 | =B | D | | D41476J | 3 | | | 001-099 |
| 0019 | 18 | | GA | | 6-0 | 24-51-25 | C04359 | =B | D | | D41476J | 3 | | | 115-199 |
| 0022 | 10 | | HA | | 2-0 | 24-53-51 | C01203 | =B | D | * | C04367 | =B | D | | ALL |
| 0023 | 22 | | GA | | 5-0 | 33-22-11 | C04366 | =L | D | | TB0047Z | 33 | BJ | | 001-099 |
| 0023 | 22 | | GA | | 6-0 | 33-22-11 | C04366 | CAP | Y | | TB0047Z | 33 | BJ | | 115-199 |
| 0110 | 18 | | GA | | 4-0 | 33-31-41 | C04146 | =L | D | | D41476J | 10 | | | 001-099 |
| 0110 | 18 | | GA | | 5-0 | 33-31-41 | C04146 | =L | D | | D41476J | 10 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1190

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1196 | 286N1196 | | | P34 CB SIDE PANEL INTERNAL WIRING (continued) | | | | | | | | | | | |
| 0201 | 20 | | GA | | 4-0 | 33-21-51 | C01203 | =L | D | | D41474J | 11 | | | 001-099 |
| 0201 | 22 | | GA | | 5-0 | 33-21-11 | C01203 | =L | D | | D41474J | 11 | | | 115-199 |
| 0202 | 22 | | GA | | 5-0 | 33-21-51 | C04359 | =L | D | | TB0047Y | A030 | BJ | | 001-099 |
| 0202 | 22 | | GA | | 5-0 | 33-21-51 | C04359 | CAP | Y | | TB0047Y | A030 | BJ | | 115-199 |
| 0300 | 16 | | GA | | 4-0 | 33-26-11 | C01270 | =L | D | | D41472J | 41 | 16 | | 001-099 |
| 0300 | 22 | | GA | | 4-0 | 33-26-11 | C01270 | =L | D | | D41472J | 41 | | | 115-199 |
| 0303 | 22 | | GA | | 4-0 | 33-31-11 | C01205 | =L | D | | D41472J | 12 | | | ALL |
| 0304 | 22 | | GA | | 4-0 | 33-26-31 | C04095 | =L | D | | D41472J | 13 | | | ALL |
| 0305 | 22 | | GA | | 4-0 | 33-31-41 | C01257 | =L | D | | D41472J | 14 | | | ALL |
| 0402 | 22 | | GA | | 4-0 | 33-11-31 | C01213 | =L | D | | D41470J | 22 | | | ALL |
| ZZAB | 02 | | ZB | | 0-0 | 24-53-51 | C01269 | =B | D | | C01213 | =B | D | | ALL |
| ZZAC | 02 | | ZB | | 0-0 | 24-53-51 | C01253 | =B | D | | C04219 | =B | D | | ALL |
| ZZAD | 02 | | ZB | | 0-0 | 24-53-51 | C04218 | =B | D | | C01296 | =B | D | | ALL |
| ZZAE | 02 | | ZB | | 0-0 | 24-53-51 | C04095 | =B | D | | C01270 | =B | D | | ALL |
| ZZAF | 02 | | ZB | | 0-0 | 24-53-51 | C04146 | =B | D | | C01257 | =B | D | | ALL |
| ZZBC | 03 | | ZB | | 0-0 | 24-51-25 | C04359 | =B | D | | C04366 | =B | D | | ALL |
| ZZBD | 00 | | ZB | | 0-0 | 24-51-25 | C04360 | =B | D | | C04366 | =B | D | | ALL |
| ZZBE | 00 | | ZB | | 0-0 | 24-51-25 | C04359 | =B | D | | C04360 | =B | D | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1190

Page 4 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | INTERNAL P33 - PLATE D | | | | | | | | | | | |
| 0001 | 22 | | GA | | 1-11 | 27-51-21 | D02478 | | B2 | | TB0080Y | A001 | BJ | | 001-099 |
| 0001 | 22 | | GA | | 2-0 | 27-51-21 | D02478 | | B2 | | TB0080Y | A001 | BJ | | 115-199 |
| 0002 | 22 | | GA | | 1-11 | 27-51-21 | D02478 | | X1 | | TB0080Y | A001 | BJ | | 001-099 |
| 0002 | 22 | | GA | | 2-0 | 27-51-21 | D02478 | | X1 | | TB0080Y | A001 | BJ | | 115-199 |
| 0003 | 22 | | GA | | 3-5 | 27-51-21 | D41424J | | 30 | | TB0080Y | A001 | BJ | | 001-099 |
| 0003 | 22 | | GA | | 3-10 | 27-51-21 | D41424J | | 30 | | TB0080Y | A001 | BJ | | 115-199 |
| 0004 | 22 | | GA | | 1-11 | 27-51-21 | D02478 | | A2 | | TB0080Y | A001 | BJ | | 001-099 |
| 0004 | 22 | | GA | | 2-0 | 27-51-21 | D02478 | | A2 | | TB0080Y | A001 | BJ | | 115-199 |
| 0005 | 22 | | GA | | 1-11 | 27-51-21 | D02478 | | X2 | | TB0080Y | A004 | BJ | | 001-099 |
| 0005 | 22 | | GA | | 2-0 | 27-51-21 | D02478 | | X2 | | TB0080Y | C008 | BJ | | 115-199 |
| 0006 | 22 | | GA | | 4-0 | 27-51-21 | D02478 | | B3 | | D41692J | 9 | | | 001-099 |
| 0006 | 22 | | GA | | 3-11 | 27-51-21 | D02478 | | B3 | | D41692J | 9 | | | 115-199 |
| 0007 | 22 | | GA | | 4-0 | 27-51-21 | D02478 | | A1 | | D41692J | 6 | | | 001-099 |
| 0007 | 22 | | GA | | 3-11 | 27-51-21 | D02478 | | A1 | | D41692J | 6 | | | 115-199 |
| 0009 | 22 | | GA | | 4-1 | 27-51-31 | D41426J | | 2 | | TB0080Y | C001 | BJ | | 001-099 |
| 0009 | 22 | | GA | | 4-10 | 27-51-31 | D41426J | | 7 | | TB0080Y | C001 | BJ | | 115-199 |
| 0010 | 22 | | GA | | 1-10 | 27-51-31 | D02986 | | A2 | | TB0080Y | C001 | BJ | | 001-099 |
| 0010 | 22 | | GA | | 1-11 | 27-51-31 | D02986 | | A2 | | TB0080Y | C001 | BJ | | 115-199 |
| 0011 | 22 | | GA | | 1-10 | 27-51-31 | D02986 | | X1 | | TB0080Y | C001 | BJ | | 001-099 |
| 0011 | 22 | | GA | | 1-11 | 27-51-31 | D02986 | | X1 | | TB0080Y | C001 | BJ | | 115-199 |
| 0012 | 22 | | GA | | 4-3 | 27-51-31 | D02986 | | X2 | | D41704J | 26 | | | 001-099 |
| 0012 | 22 | | GA | | 4-8 | 27-51-31 | D02986 | | X2 | | D41704J | 26 | | | 115-199 |
| 0013 | 22 | | GA | | 4-3 | 27-51-31 | D02986 | | A1 | | D41704J | 5 | | | 001-099 |
| 0013 | 22 | | GA | | 4-8 | 27-51-31 | D02986 | | A1 | | D41704J | 5 | | | 115-199 |
| 0014 | 22 | | GA | | 4-9 | 28-21-11 | D41426J | | 6 | | D02390 | A3 | | | 001-099 |
| 0014 | 22 | | GA | | 5-1 | 28-21-11 | D41426J | | 6 | | D02390 | A3 | | | 115-199 |
| 0015 | 22 | | GA | | 4-1 | 28-21-11 | D41424J | | 3 | | D02390 | B3 | | | ALL |
| 0018 | 18 | | GA | | 2-5 | 28-21-11 | TB0080G | | 9 | 2 | D02390 | A1 | | | 001-099 |
| 0018 | 20 | | GA | | 2-3 | 28-21-11 | TB0080Y | | A009 | BJ | D02390 | A1 | | | 115-199 |
| 0019 | 18 | | GA | | 4-10 | 28-21-11 | D41420J | | 10 | 18 | D02390 | B1 | | | 001-099 |
| 0019 | 20 | | GA | | 2-3 | 28-21-11 | TB0080G | | 13 | 2 | D02390 | B1 | | | 115-199 |
| 0020 | 18 | | GA | | 2-9 | 28-21-11 | D41424J | | 8 | | D02392 | A3 | | | 001-099 |
| 0020 | 18 | | GA | | 2-11 | 28-21-11 | D41424J | | 7 | 18 | D02392 | A3 | | | 115-199 |
| 0021 | 18 | | GA | | 2-9 | 28-21-11 | D41424J | | 4 | | D02392 | C3 | | | 001-099 |
| 0021 | 18 | | GA | | 2-11 | 28-21-11 | D41424J | | 5 | 18 | D02392 | C3 | | | 115-199 |
| 0022 | 18 | | GA | | 4-6 | 28-21-11 | D42006J | | 15 | 18 | D02390 | A2 | | | 001-099 |
| 0022 | 22 | | GA | | 8-2 | 28-21-11 | TB0046Y | | C006 | BJ | D02390 | A2 | | | 115-199 |
| 0027 | 20 | | GA | | 2-5 | 28-41-11 | TB0080G | | 13 | 2 | D02394 | C2 | | | 001-099 |
| 0027 | 20 | | GA | | 2-4 | 28-41-11 | TB0080G | | 13 | 2 | D02394 | C2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 0028 | 18 | | GA | | 2-4 | 28-21-11 | TB0080G | 8 | 2 | | D02394 | A2 | | | 001-099 |
| 0028 | 20 | | GA | | 2-4 | 28-21-11 | TB0080Y | C004 | BJ | | D02394 | A2 | | | 115-199 |
| 0029 | 18 | | GA | | 8-2 | 28-21-11 | TB0046H | 18 | 2 | | D02394 | A1 | | | 001-099 |
| 0029 | 20 | | GA | | 8-3 | 28-21-11 | TB0046Z | 18 | BJ | | D02394 | A1 | | | 115-199 |
| 0030 | 20 | | GA | | 4-7 | 28-41-11 | D41704J | 17 | | | D02394 | C1 | | | 001-099 |
| 0030 | 22 | | GA | | 4-4 | 28-41-11 | D41704J | 17 | | | D02394 | C1 | | | 115-199 |
| 0031 | 18 | | GA | | 4-5 | 28-21-11 | D41718J | 6 | 18 | | D02394 | X2 | | | 001-099 |
| 0031 | 22 | | GA | | 4-4 | 28-21-11 | D41718J | 6 | | | D02394 | X2 | | | 115-199 |
| 0032 | 18 | | GA | | 2-4 | 28-21-11 | TB0080G | 8 | 2 | | D02394 | X1 | | | 001-099 |
| 0032 | 22 | | GA | | 2-4 | 28-21-11 | TB0080Y | C004 | BJ | | D02394 | X1 | | | 115-199 |
| 0035 | 18 | | GA | | 5-6 | 28-21-11 | TB0046H | 18 | 2 | | D41718J | 4 | 18 | | 001-099 |
| 0035 | 20 | | GA | | 6-2 | 28-21-11 | TB0046Z | 18 | BJ | | D41718J | 4 | | | 115-199 |
| 0036 | 18 | | GA | | 8-2 | 28-21-11 | TB0046H | 18 | 2 | | D02390 | X1 | | | 001-099 |
| 0036 | 20 | | GA | | 8-2 | 28-21-11 | TB0046Z | 18 | BJ | | D02390 | X1 | | | 115-199 |
| 0037 | 18 | | GA | | 2-7 | 28-21-11 | GD00450 | DC.. | 2 | | D02390 | X2 | | | 001-099 |
| 0037 | 20 | | GA | | 2-4 | 28-21-11 | GD00450 | DC.. | 2 | | D02390 | X2 | | | 115-199 |
| 0038 | 18 | | GA | | 4-4 | 28-21-11 | D41718J | 7 | 18 | | D02390 | B2 | | | 001-099 |
| 0038 | 20 | | GA | | 8-2 | 28-21-11 | D41718J | 7 | | | D02390 | B2 | | | 115-199 |
| 0039 | 22 | | GA | | 4-0 | 28-21-21 | D02512 | A1 | | | D41424J | 7 | | | 001-099 |
| 0039 | 20 | | GA | | 4-1 | 28-21-21 | D02512 | A1 | | | D41424J | 8 | | | 115-199 |
| 0040 | 20 | | GA | | 1-3 | 28-21-21 | D02512 | B2 | | | D04586 | B1 | | | 001-099 |
| 0040 | 20 | | GA | | 1-1 | 28-21-21 | D02512 | B2 | | | D04586 | B1 | | | 115-199 |
| 0041 | 22 | | GA | | 2-1 | 28-21-21 | D02512 | A2 | | | TB0080Y | A003 | BJ | | 001-099 |
| 0041 | 22 | | GA | | 2-2 | 28-21-21 | D02512 | A2 | | | TB0080Y | A003 | BJ | | 115-199 |
| 0042 | 22 | | GA | | 2-1 | 28-21-21 | D02512 | X2 | | | TB0080Y | A003 | BJ | | 001-099 |
| 0042 | 22 | | GA | | 2-2 | 28-21-21 | D02512 | X2 | | | TB0080Y | A003 | BJ | | 115-199 |
| 0043 | 22 | | GA | | 3-9 | 28-21-21 | D41718J | 8 | | | TB0080Y | A003 | BJ | | 001-099 |
| 0043 | 22 | | GA | | 4-1 | 28-21-21 | D41718J | 8 | | | TB0080Y | A003 | BJ | | 115-199 |
| 0044 | 20 | | GA | | 4-3 | 28-21-22 | D02448 | X1 | | | D41718J | 13 | | | 001-099 |
| 0044 | 20 | | GA | | 4-2 | 28-21-22 | D02448 | X1 | | | D41718J | 13 | | | 115-199 |
| 0045 | 20 | | GA | | 4-3 | 28-21-22 | D02448 | X2 | | | D41718J | 9 | | | 001-099 |
| 0045 | 20 | | GA | | 4-2 | 28-21-22 | D02448 | X2 | | | D41718J | 9 | | | 115-199 |
| 0046 | 20 | | GA | | 3-9 | 28-21-22 | D41718J | 14 | | | TB0080Y | C003 | BJ | | 001-099 |
| 0046 | 20 | | GA | | 4-1 | 28-21-22 | D41718J | 14 | | | TB0080Y | C003 | BJ | | 115-199 |
| 0047 | 20 | | GA | | 2-2 | 28-21-22 | D02448 | A2 | | | TB0080H | 5 | 2 | | 001-099 |
| 0047 | 20 | | GA | | 2-1 | 28-21-22 | D02448 | A2 | | | TB0080Z | 5 | BJ | | 115-199 |
| 0048 | 20 | | GA | | 1-7 | 28-21-22 | D02450 | X1 | | | TB0080Y | C003 | BJ | | 001-099 |
| 0048 | 20 | | GA | | 1-9 | 28-21-22 | D02450 | X1 | | | TB0080Y | C003 | BJ | | 115-199 |
| 0049 | 20 | | GA | | 3-10 | 28-21-22 | D02450 | X2 | | | D41718J | 10 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 0050 | 20 | | GA | | 1-9 | 28-21-22 | | D02450 | | A2 | | TB0080H | 5 | 2 | | 001-099 |
| 0050 | 20 | | GA | | 1-9 | 28-21-22 | | D02450 | | A2 | | TB0080Z | 5 | BJ | | 115-199 |
| 0051 | 20 | | GA | | 2-1 | 28-21-22 | | D02506 | | X1 | | TB0080Y | C003 | BJ | | 001-099 |
| 0051 | 20 | | GA | | 2-2 | 28-21-22 | | D02506 | | X1 | | TB0080Y | C003 | BJ | | 115-199 |
| 0052 | 20 | | GA | | 4-4 | 28-21-22 | | D02506 | | X2 | | D41718J | 11 | | | 001-099 |
| 0052 | 20 | | GA | | 4-3 | 28-21-22 | | D02506 | | X2 | | D41718J | 11 | | | 115-199 |
| 0053 | 20 | | GA | | 2-3 | 28-21-22 | | D02506 | | A2 | | TB0080H | 5 | 2 | | 001-099 |
| 0053 | 20 | | GA | | 2-2 | 28-21-22 | | D02506 | | A2 | | TB0080Z | 5 | BJ | | 115-199 |
| 0054 | 20 | | GA | | 3-11 | 28-21-22 | | D02504 | | X1 | | D41718J | 15 | | | ALL |
| 0055 | 20 | | GA | | 3-11 | 28-21-22 | | D02504 | | X2 | | D41718J | 12 | | | ALL |
| 0056 | 20 | | GA | | 1-10 | 28-21-22 | | D02504 | | A2 | | TB0080H | 5 | 2 | | 001-099 |
| 0056 | 20 | | GA | | 1-10 | 28-21-22 | | D02504 | | A2 | | TB0080Z | 5 | BJ | | 115-199 |
| 0057 | 20 | | GA | | 4-3 | 28-21-23 | | D41718J | | 19 | | D02448 | A1 | | | 001-099 |
| 0057 | 20 | | GA | | 4-2 | 28-21-23 | | D41718J | | 19 | | D02448 | A1 | | | 115-199 |
| 0058 | 20 | | GA | | 3-10 | 28-21-23 | | D41718J | | 17 | | D02450 | A1 | | | ALL |
| 0059 | 20 | | GA | | 4-4 | 28-21-23 | | D41718J | | 18 | | D02506 | A1 | | | 001-099 |
| 0059 | 20 | | GA | | 4-3 | 28-21-23 | | D41718J | | 18 | | D02506 | A1 | | | 115-199 |
| 0060 | 20 | | GA | | 3-11 | 28-21-23 | | D41718J | | 20 | | D02504 | A1 | | | ALL |
| 0061 | 22 | | GA | | 4-7 | 28-26-11 | | D02626 | | A2 | | D41870J | 25 | | | 001-099 |
| 0061 | 20 | | GA | | 5-0 | 28-26-11 | | D02626 | | A2 | | D41870J | 25 | | | 115-199 |
| 0062 | 20 | | GA | | 4-3 | 28-26-11 | | D02626 | | B2 | | D41718J | 22 | | | 001-099 |
| 0062 | 20 | | GA | | 4-2 | 28-26-11 | | D02626 | | B2 | | D41718J | 22 | | | 115-199 |
| 0063 | 20 | | GA | | 4-3 | 28-26-11 | | D02626 | | X1 | | D41718J | 23 | | | 001-099 |
| 0063 | 20 | | GA | | 4-2 | 28-26-11 | | D02626 | | X1 | | D41718J | 23 | | | 115-199 |
| 0064 | 22 | | GA | | 4-3 | 28-26-11 | | D02626 | | A1 | | D41718J | 27 | | | 001-099 |
| 0064 | 20 | | GA | | 4-2 | 28-26-11 | | D02626 | | A1 | | D41718J | 27 | | | 115-199 |
| 0065 | 22 | | GA | | 4-3 | 28-26-11 | | D02626 | | A3 | | D41718J | 28 | | | 001-099 |
| 0065 | 20 | | GA | | 4-2 | 28-26-11 | | D02626 | | A3 | | D41718J | 28 | | | 115-199 |
| 0066 | 20 | | GA | | 2-3 | 28-26-11 | | D02626 | | B1 | | D02628 | 5 | | | 001-099 |
| 0066 | 20 | | GA | | 2-2 | 28-26-11 | | D02626 | | B1 | | D02628 | 5 | | | 115-199 |
| 0067 | 20 | | GA | | 2-3 | 28-26-11 | | D02626 | | B3 | | D02628 | 4 | | | 001-099 |
| 0067 | 20 | | GA | | 2-2 | 28-26-11 | | D02626 | | B3 | | D02628 | 4 | | | 115-199 |
| 0068 | 20 | | GA | | 1-3 | 28-26-11 | | D02628 | | 2 | | GD00450 | DC.. | 2 | | 001-099 |
| 0068 | 20 | | GA | | 1-2 | 28-26-11 | | D02628 | | 2 | | GD00450 | DC.. | 2 | | 115-199 |
| 0069 | 22 | | GA | | 1-3 | 28-26-11 | | D02628 | | 3 | | GD00450 | DC.. | 2 | | 001-099 |
| 0069 | 20 | | GA | | 1-2 | 28-26-11 | | D02628 | | 3 | | GD00450 | DC.. | 2 | | 115-199 |
| 0070 | 22 | | GA | | 4-0 | 28-26-11 | | D02628 | | 7 | | D41718J | 26 | | | 001-099 |
| 0070 | 20 | | GA | | 4-1 | 28-26-11 | | D02628 | | 7 | | D41718J | 26 | | | 115-199 |
| 0072 | 20 | | GA | | 5-6 | 28-26-11 | | TB0046H | | 18 | 2 | D41718J | 21 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 0072 | 20 | | GA | | 6-2 | 28-26-11 | TB0046Z | 18 | BJ | | D41718J | 21 | | | 115-199 |
| 0073 | 20 | | GA | | 4-3 | 28-26-11 | D02716 | | B2 | | D41718J | 24 | | | ALL |
| 0074 | 20 | | GA | | 4-3 | 28-26-11 | D02716 | | X1 | | D41718J | 25 | | | ALL |
| 0075 | 22 | | GA | | 4-6 | 28-26-11 | D02716 | | A1 | | D41704J | 12 | | | 001-099 |
| 0075 | 20 | | GA | | 4-11 | 28-26-11 | D02716 | | A1 | | D41704J | 12 | | | 115-199 |
| 0076 | 22 | | GA | | 4-6 | 28-26-11 | D02716 | | A3 | | D41704J | 13 | | | 001-099 |
| 0076 | 20 | | GA | | 4-11 | 28-26-11 | D02716 | | A3 | | D41704J | 13 | | | 115-199 |
| 0077 | 22 | | GA | | 4-8 | 28-26-11 | D02716 | | A2 | | D41870J | 26 | | | 001-099 |
| 0077 | 20 | | GA | | 5-1 | 28-26-11 | D02716 | | A2 | | D41870J | 26 | | | 115-199 |
| 0078 | 20 | | GA | | 2-6 | 28-26-11 | D02716 | | X2 | | GD00450 | DC.. | 2 | | 001-099 |
| 0078 | 20 | | GA | | 2-3 | 28-26-11 | D02716 | | X2 | | GD00450 | DC.. | 2 | | 115-199 |
| 0079 | 20 | | GA | | 2-5 | 28-26-11 | D02718 | | 4 | | D02716 | B3 | | | 001-099 |
| 0079 | 20 | | GA | | 2-2 | 28-26-11 | D02718 | | 4 | | D02716 | B3 | | | 115-199 |
| 0080 | 20 | | GA | | 2-5 | 28-26-11 | D02718 | | 5 | | D02716 | B1 | | | 001-099 |
| 0080 | 20 | | GA | | 2-2 | 28-26-11 | D02718 | | 5 | | D02716 | B1 | | | 115-199 |
| 0081 | 20 | | GA | | 1-1 | 28-26-11 | D02718 | | 2 | | GD00450 | DC.. | 2 | | 001-099 |
| 0081 | 20 | | GA | | 1-2 | 28-26-11 | D02718 | | 2 | | GD00450 | DC.. | 2 | | 115-199 |
| 0082 | 22 | | GA | | 1-1 | 28-26-11 | D02718 | | 3 | | GD00450 | DC.. | 2 | | 001-099 |
| 0082 | 20 | | GA | | 1-2 | 28-26-11 | D02718 | | 3 | | GD00450 | DC.. | 2 | | 115-199 |
| 0083 | 22 | | GA | | 4-4 | 28-26-11 | D02718 | | 7 | | D41704J | 14 | | | 001-099 |
| 0083 | 20 | | GA | | 4-9 | 28-26-11 | D02718 | | 7 | | D41704J | 14 | | | 115-199 |
| 0084 | 20 | | GA | | 6-2 | SPARE | D42006J | | 14 | | TB0046Y | C006 | BJ | | 115-199 |
| 0085 | 20 | | GA | | 6-2 | SPARE | D41718J | | 1 | | TB0046Y | C005 | BJ | | 115-199 |
| 0086 | 22 | | GA | | 6-2 | SPARE | D41718J | | 2 | | TB0046Y | C005 | BJ | | 115-199 |
| 0128 | 22 | | GA | | 4-0 | 27-51-21 | TB0080Y | A004 | BJ | | D41412J | 20 | | | 001-099 |
| 0128 | 22 | | GA | | 5-0 | 27-51-21 | TB0080Y | C008 | BJ | | D41412J | 20 | | | 115-199 |
| 0133 | 20 | | PA | | 5-0 | 28-22-11 | D41870J | | 31 | | D11714 | B2 | | | ALL |
| 0134 | 20 | | PA | | 4-0 | 28-22-11 | D11714 | | B3 | | K10875 | X1 | C | | ALL |
| 0135 | 20 | | PA | | 4-0 | 28-22-11 | K10875 | | X2 | C | GD00452 | AC.. | 2 | | ALL |
| 0137 | 22 | | GA | | 4-0 | 27-51-21 | D41692J | | 8 | | D02478 | A3 | | | 001-099 |
| 0137 | 22 | | GA | | 3-11 | 27-51-21 | D41692J | | 8 | | D02478 | A3 | | | 115-199 |
| 0139 | 22 | | GA | | 3-7 | 27-51-21 | D41692J | | 11 | | TB0080Y | A004 | BJ | | 001-099 |
| 0139 | 22 | | GA | | 3-11 | 27-51-21 | D41692J | | 11 | | TB0080Y | C008 | BJ | | 115-199 |
| 0140 | 22 | | GA | | 4-0 | 27-51-21 | D41692J | | 10 | | D02478 | B1 | | | 001-099 |
| 0140 | 22 | | GA | | 3-11 | 27-51-21 | D41692J | | 10 | | D02478 | B1 | | | 115-199 |
| 0143 | 20 | | GA | | 2-5 | 28-26-11 | D02626 | | X2 | | GD00450 | DC.. | 2 | | 001-099 |
| 0143 | 20 | | GA | | 2-3 | 28-26-11 | D02626 | | X2 | | GD00450 | DC.. | 2 | | 115-199 |
| 0144 | 22 | | GA | | 6-2 | 28-21-11 | D42006J | | 15 | | TB0046Y | C006 | BJ | | 115-199 |
| 0145 | 18 | | GA | | 2-9 | 28-21-11 | D41424J | | 6 | | D02392 | B3 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 0145 | 18 | | GA | | 2-11 | 28-21-11 | D41424J | | 6 | | D02392 | | B3 | | 115-199 |
| 0146 | 18 | | GA | | 2-0 | 28-21-22 | D02392 | | B2 | | TB0080H | 5 | 2 | | 001-099 |
| 0146 | 20 | | GA | | 2-1 | 28-21-22 | D02392 | | B2 | | TB0080Z | 5 | BJ | | 115-199 |
| 0147 | 18 | | GA | | 2-1 | 28-21-11 | D02392 | | A2 | | TB0080G | 9 | 2 | | 001-099 |
| 0147 | 20 | | GA | | 2-1 | 28-21-11 | D02392 | | A2 | | TB0080Y | A009 | BJ | | 115-199 |
| 0148 | 18 | | GA | | 2-1 | 28-21-11 | D02392 | | A1 | | TB0080G | 13 | 2 | | 001-099 |
| 0148 | 20 | | GA | | 2-1 | 28-21-11 | D02392 | | A1 | | TB0080G | 13 | 2 | | 115-199 |
| 0149 | 18 | | GA | | 3-6 | 28-21-11 | D41420J | | 3 | 18 | D02392 | | B1 | | ALL |
| 0150 | 18 | | GA | | 4-6 | 28-21-11 | D41420J | | 1 | 18 | TB0080G | 13 | 2 | | ALL |
| 0151 | 22 | | GA | | 6-2 | SPARE | D41718J | CAP | | Y | TB0046Y | C005 | BJ | | 115-199 |
| 0152 | 20 | | GA | | 3-0 | 28-21-11 | D41718J | | 3 | | D02392 | | X2 | | 001-099 |
| 0152 | 20 | | GA | | 3-1 | 28-21-11 | D41718J | | 3 | | D02392 | | X2 | | 115-199 |
| 0153 | 20 | | GA | | 4-3 | 28-21-22 | D02512 | | B1 | | D41718J | 16 | | | ALL |
| 0154 | 18 | | GA | | 4-1 | 28-22-11 | D02394 | | D1 | | D41424J | 1 | | | 001-099 |
| 0154 | 18 | | GA | | 4-2 | 28-22-11 | D02394 | | D1 | | D41424J | 1 | | | 115-199 |
| 0157 | 18 | | GA | | 4-1 | 28-22-11 | D02394 | | D2 | | D41424J | 2 | | | 001-099 |
| 0157 | 18 | | GA | | 4-2 | 28-22-11 | D02394 | | D2 | | D41424J | 2 | | | 115-199 |
| 0160 | 20 | | GA | | 4-7 | 28-41-14 | D41704J | | 15 | | D02394 | | B2 | | 001-099 |
| 0160 | 20 | | GA | | 5-1 | 28-41-14 | D41704J | | 15 | | D02394 | | B2 | | 115-199 |
| 0161 | 20 | | GA | | 4-7 | 28-41-14 | D41704J | | 16 | | D02394 | | B1 | | 001-099 |
| 0161 | 20 | | GA | | 5-1 | 28-41-14 | D41704J | | 16 | | D02394 | | B1 | | 115-199 |
| 0162 | 20 | | GA | | 2-5 | 28-41-11 | TB0080G | | 9 | 2 | D02390 | | C2 | | 001-099 |
| 0162 | 20 | | GA | | 5-0 | 28-41-11 | TB0080Y | A009 | | BJ | D02390 | | C2 | | 115-199 |
| 0163 | 20 | | GA | | 4-7 | 28-41-11 | D41704J | | 18 | | D02390 | | C1 | | 001-099 |
| 0163 | 20 | | GA | | 5-0 | 28-41-11 | D41704J | | 18 | | D02390 | | C1 | | 115-199 |
| 0164 | 22 | | GA | | 8-1 | 28-21-21 | D02512 | | X1 | | TB0046H | 18 | 2 | | 001-099 |
| 0164 | 22 | | GA | | 8-2 | 28-21-21 | D02512 | | X1 | | TB0046Z | 18 | BJ | | 115-199 |
| 0165 | 20 | | GA | | 5-2 | 28-21-21 | D41424J | | 9 | | TB0046H | 18 | 2 | | 001-099 |
| 0165 | 20 | | GA | | 5-4 | 28-21-21 | D41424J | | 9 | | TB0046Z | 18 | BJ | | 115-199 |
| 0166 | 18 | | GA | | 2-0 | 28-21-11 | D02392 | | C2 | | TB0080G | 8 | 2 | | 001-099 |
| 0166 | 20 | | GA | | 2-1 | 28-21-11 | D02392 | | C2 | | TB0080Y | C004 | BJ | | 115-199 |
| 0167 | 18 | | GA | | 2-0 | 28-21-11 | D02392 | | C1 | | TB0080G | 7 | 2 | | 001-099 |
| 0167 | 20 | | GA | | 2-1 | 28-21-11 | D02392 | | C1 | | TB0080Y | C002 | BJ | | 115-199 |
| 0168 | 18 | | GA | | 2-0 | 28-21-11 | D02392 | | X1 | | TB0080G | 7 | 2 | | 001-099 |
| 0168 | 20 | | GA | | 2-1 | 28-21-11 | D02392 | | X1 | | TB0080Y | C002 | BJ | | 115-199 |
| 0169 | 18 | | GA | | 4-5 | 28-21-11 | D41420J | | 2 | 18 | TB0080G | 7 | 2 | | 001-099 |
| 0169 | 20 | | GA | | 4-6 | 28-21-11 | D41420J | | 2 | | TB0080Y | C002 | BJ | | 115-199 |
| 0170 | 18 | | GA | | 8-1 | 28-22-11 | D02390 | | D2 | | TB0046G | 16 | 2 | | 001-099 |
| 0170 | 18 | | GA | | 8-2 | 28-22-11 | D02390 | | D2 | | TB0046G | 16 | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | | | | | | | | | | | | | | | |
| | | 286N1230 | | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | |
| 0171 | 18 | GA | | | 8-1 | 28-22-11 | D02390 | D1 | | | TB0046G | 15 | 2 | | 001-099 |
| 0171 | 18 | GA | | | 8-2 | 28-22-11 | D02390 | D1 | | | TB0046G | 15 | 2 | | 115-199 |
| 0172 | 16 | GA | | | 3-1 | 29-11-12 | D03114 | A1 | | | D41412J | 15 | 16 | | 001-099 |
| 0172 | 16 | GA | | | 3-10 | 29-11-12 | D03114 | A1 | | | D41412J | 15 | 16 | | 115-199 |
| 0173 | 16 | GA | | | 3-1 | 29-11-12 | D03114 | A2 | | | D41412J | 12 | 16 | | 001-099 |
| 0173 | 16 | GA | | | 3-10 | 29-11-12 | D03114 | A2 | | | D41412J | 12 | 16 | | 115-199 |
| 0174 | 22 | GA | | | 3-1 | 29-11-12 | D03114 | X1 | | | D41412J | 13 | | | 001-099 |
| 0174 | 22 | GA | | | 3-10 | 29-11-12 | D03114 | X1 | | | D41412J | 13 | | | 115-199 |
| 0175 | 22 | GA | | | 2-5 | 29-11-12 | D03114 | X2 | | | M00499 | A | C | | 001-099 |
| 0175 | 22 | GA | | | 3-3 | 29-11-12 | D03114 | X2 | | | M00499 | A | C | | 115-199 |
| 0176 | 22 | GA | | | 2-10 | 29-11-12 | GD00450 | DC.. | 2 | | M00499 | B | C | | 001-099 |
| 0176 | 22 | GA | | | 3-10 | 29-11-12 | GD00450 | DC.. | 2 | | M00499 | B | C | | 115-199 |
| 0181 | 22 | GA | | | 7-4 | 29-22-11 | M10146 | A | C | | D42094J | 5 | | | 115-199 |
| 0183 | 22 | GA | | | 0-7 | 29-22-11 | M10145 | B | C | * | M10146 | B | C | | 115-199 |
| 0184 | 22 | GA | | | 3-11 | 29-22-11 | D41414J | 5 | | | TB0080Y | A010 | BJ | | 001-099 |
| 0184 | 22 | GA | | | 4-5 | 29-22-11 | D41414J | 5 | | | TB0080Y | A010 | BJ | | 115-199 |
| 0185 | 22 | GA | | | 4-11 | 29-22-11 | D41414J | 9 | | | TB0046A | C003 | 2 | | 001-099 |
| 0185 | 20 | GA | | | 4-5 | 29-22-11 | D41414J | 9 | | | TB0080Y | C010 | BJ | | 115-199 |
| 0186 | 22 | GA | | | 2-5 | 29-22-11 | D03130 | A2 | | | TB0080Y | A010 | BJ | | ALL |
| 0187 | 22 | GA | | | 2-8 | 29-22-11 | D03130 | A3 | | | D41950J | 7 | | | 001-099 |
| 0187 | 22 | GA | | | 3-5 | 29-22-11 | D03130 | A3 | | | D41950J | 7 | | | 115-199 |
| 0188 | 22 | GA | | | 6-3 | 29-22-11 | D03130 | A1 | | | TB0046A | A003 | 2 | | 001-099 |
| 0188 | 22 | GA | | | 6-7 | 29-22-11 | D03130 | A1 | | | TB0046A | A003 | 2 | | 115-199 |
| 0189 | 22 | GA | | | 2-5 | 29-22-11 | D03130 | X1 | | | TB0080Y | A010 | BJ | | ALL |
| 0190 | 22 | GA | | | 4-3 | 29-22-11 | D03130 | X2 | | | D42094J | 8 | | | 001-099 |
| 0190 | 22 | GA | | | 4-7 | 29-22-11 | D03130 | X2 | | | D42094J | 3 | | | 115-199 |
| 0191 | 20 | GA | | | 6-2 | 29-22-11 | D42006J | 11 | | | M10145 | B | C | * | 115-199 |
| 0192 | 22 | GA | | | 5-7 | 29-22-11 | TB0046A | C003 | 2 | | D41950J | 8 | | | 001-099 |
| 0192 | 22 | GA | | | 4-9 | 29-22-11 | TB0080Y | C010 | BJ | | D41950J | 8 | | | 115-199 |
| 0196 | 20 | GA | | | 4-11 | 26-21-11 | D41414J | 16 | | | TB0046Y | A007 | BJ | | 001-099 |
| 0196 | 20 | GA | | | 5-5 | 26-21-11 | D41414J | 16 | | | TB0046Y | A007 | BJ | | 115-199 |
| 0197 | 20 | GA | | | 5-2 | 26-21-11 | D42006J | 8 | | | TB0046Y | A007 | BJ | | 001-099 |
| 0197 | 20 | GA | | | 6-2 | 26-21-11 | D42006J | 8 | | | TB0046Y | A007 | BJ | | 115-199 |
| 0198 | 20 | GA | | | 5-2 | 26-21-11 | D42006J | 5 | | | TB0046Y | A007 | BJ | | 001-099 |
| 0198 | 20 | GA | | | 6-2 | 26-21-11 | D42006J | 5 | | | TB0046Y | A007 | BJ | | 115-199 |
| 0199 | 22 | GA | | | 4-10 | 29-22-11 | D42094J | 8 | | | TB0046Y | A008 | BJ | | 115-199 |
| 0204 | 22 | GA | | | 2-2 | 28-21-21 | D04586 | A3 | | | TB0080Y | A003 | BJ | | 001-099 |
| 0204 | 22 | GA | | | 2-4 | 28-21-21 | D04586 | A3 | | | TB0080Y | A003 | BJ | | 115-199 |
| 0205 | 22 | GA | | | 8-2 | 28-21-21 | D04586 | X1 | | | TB0046H | 18 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 0205 | 22 | | GA | | 8-3 | 28-21-21 | D04586 | | X1 | | TB0046Z | 18 | BJ | | 115-199 |
| 0206 | 22 | | GA | | 2-2 | 28-21-21 | D04586 | | X2 | | GD00451 | DC.. | 2 | | 001-099 |
| 0206 | 22 | | GA | | 1-11 | 28-21-21 | D04586 | | X2 | | GD00451 | DC.. | 2 | | 115-199 |
| 0207 | 22 | | GA | | 2-2 | 28-21-21 | D04586 | | A2 | | GD00451 | DC.. | 2 | | 001-099 |
| 0207 | 22 | | GA | | 1-11 | 28-21-21 | D04586 | | A2 | | GD00451 | DC.. | 2 | | 115-199 |
| 0208 | 20 | | GA | | 2-4 | 28-21-21 | D04586 | | B2 | | TB0080G | 8 | 2 | | 001-099 |
| 0208 | 20 | | GA | | 2-4 | 28-21-21 | D04586 | | B2 | | TB0080Y | C004 | BJ | | 115-199 |
| 0209 | 20 | | GA | | 4-4 | 28-26-11 | D41870J | | 24 | | TB0080H | 5 | 2 | | 001-099 |
| 0209 | 20 | | GA | | 4-11 | 28-26-11 | D41870J | | 24 | | TB0080Z | 5 | BJ | | 115-199 |
| 0210 | 20 | | GA | | 4-4 | 28-26-11 | D41870J | | 23 | | TB0080H | 5 | 2 | | 001-099 |
| 0210 | 20 | | GA | | 4-11 | 28-26-11 | D41870J | | 23 | | TB0080Z | 5 | BJ | | 115-199 |
| 0211 | 16 | | GA | | 3-3 | 29-21-31 | D03244 | | A2 | | D41426J | 7 | | | 001-099 |
| 0211 | 16 | | GA | | 4-10 | 29-21-31 | D03244 | | A2 | | D42094J | 1 | | | 115-199 |
| 0212 | 16 | | GA | | 4-5 | 29-21-31 | D03244 | | A1 | | D42094J | 6 | | | 001-099 |
| 0212 | 16 | | GA | | 4-10 | 29-21-31 | D03244 | | A1 | | D42094J | 6 | | | 115-199 |
| 0213 | 22 | | GA | | 4-5 | 29-21-31 | D03244 | | X1 | | D42094J | 2 | | | 001-099 |
| 0213 | 18 | | GA | | 4-10 | 29-21-31 | D03244 | | X1 | | D42094J | 2 | | | 115-199 |
| 0214 | 22 | | GA | | 2-5 | 29-21-31 | D03244 | | X2 | | M10323 | A | C | | 001-099 |
| 0214 | 18 | | GA | | 3-1 | 29-21-31 | D03244 | | X2 | | M10323 | A | C | | 115-199 |
| 0215 | 22 | | GA | | 6-2 | 29-21-31 | D42094J | | 7 | | M10323 | B | C | | 001-099 |
| 0215 | 18 | | GA | | 7-4 | 29-21-31 | D42094J | | 7 | | M10323 | B | C | | 115-199 |
| 0220 | 22 | | GA | | 1-10 | 29-31-11 | D41422J | | 2 | | D41704J | 3 | | | 001-099 |
| 0220 | 22 | | GA | | 2-4 | 29-31-11 | D41422J | | 2 | | D41704J | 3 | | | 115-199 |
| 0221 | 22 | | GA | | 2-0 | 29-31-11 | D41424J | | 14 | | D41722J | 4 | | | 001-099 |
| 0221 | 22 | | GA | | 2-11 | 29-31-11 | D41424J | | 14 | | D41722J | 4 | | | 115-199 |
| 0223 | 22 | | GA | | 3-7 | 32-44-11 | D41096J | | 5 | | D41426J | 5 | | | 115-199 |
| 0224 | 22 | | GA | | 4-0 | 32-44-11 | D41096J | | 8 | | D42006J | 13 | | | 115-199 |
| 0225 | 24 | | GK | | 2-1 | 27-51-31 | D41424J | | 18 | | D41704J | 11 | | | 001-099 |
| 0225 | 22 | | GA | | 2-7 | 27-51-31 | D41424J | | 18 | | D41704J | 11 | | | 115-199 |
| 0227 | 22 | | GA | | 4-5 | 29-11-12 | M10557 | | A | C | D41626J | 2 | | | 001-099 |
| 0227 | 22 | | GA | | 6-2 | 29-11-12 | M10558 | | B | C | D42006J | 29 | | | 115-199 |
| 0228 | 22 | | GA | | 4-5 | 29-11-12 | M10557 | | B | C | D41626J | 1 | | | 001-099 |
| 0228 | 22 | | GA | | 6-2 | 29-11-12 | M10557 | | B | C | D41704J | 8 | | | 115-199 |
| 0229 | 22 | | GA | | 4-3 | 29-11-12 | M10558 | | B | C | D42006J | 26 | | | 001-099 |
| 0229 | 22 | | GA | | 6-2 | 29-11-12 | M10558 | | B | C | D42006J | 26 | | | 115-199 |
| 0230 | 22 | | GA | | 4-5 | 29-11-12 | M10558 | | A | C | D41626J | 12 | | | 001-099 |
| 0230 | 22 | | GA | | 6-2 | 29-11-12 | M10558 | | A | C | D42006J | 28 | | | 115-199 |
| 0231 | 22 | | GA | | 6-1 | 27-51-21 | D05608 | | A2 | | TB0046Y | C002 | BJ | | 001-099 |
| 0231 | 22 | | GA | | 6-6 | 27-51-21 | D05608 | | A2 | | TB0046Y | C002 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | | 286N1230 | | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | |
| 0232 | 22 | GA | | | 2-6 | 27-51-21 | D05608 | A3 | | | TB0080Y | C011 | BJ | | ALL |
| 0233 | 22 | GA | | | 2-6 | 27-51-21 | D05608 | B1 | | | TB0080Y | A011 | BJ | | ALL |
| 0234 | 22 | GA | | | 2-5 | 27-51-21 | D05608 | B2 | | | D41692J | 23 | | | 001-099 |
| 0234 | 22 | GA | | | 2-6 | 27-51-21 | D05608 | B2 | | | D41692J | 23 | | | 115-199 |
| 0235 | 22 | GA | | | 2-5 | 27-51-21 | D05608 | B3 | | | D41692J | 25 | | | 001-099 |
| 0235 | 22 | GA | | | 2-6 | 27-51-21 | D05608 | B3 | | | D41692J | 25 | | | 115-199 |
| 0236 | 22 | GA | | | 2-6 | 27-51-21 | D05608 | X2 | | | TB0080Y | A011 | BJ | | ALL |
| 0237 | 22 | GA | | | 2-6 | 27-51-21 | D05608 | X1 | | | TB0080Y | C011 | BJ | | ALL |
| 0238 | 22 | GA | | | 5-7 | 27-51-21 | D41692J | 15 | | | TB0046Y | C002 | BJ | | 001-099 |
| 0238 | 22 | GA | | | 6-0 | 27-51-21 | D41692J | 15 | | | TB0046Y | C002 | BJ | | 115-199 |
| 0239 | 22 | GA | | | 3-10 | 27-51-21 | D41692J | 21 | | | TB0080Y | C011 | BJ | | 001-099 |
| 0239 | 22 | GA | | | 3-11 | 27-51-21 | D41692J | 21 | | | TB0080Y | C011 | BJ | | 115-199 |
| 0240 | 22 | GA | | | 4-0 | 27-51-21 | D41718J | 29 | | | TB0080Y | A011 | BJ | | 001-099 |
| 0240 | 22 | GA | | | 4-1 | 27-51-21 | D41718J | 29 | | | TB0080Y | A011 | BJ | | 115-199 |
| 0241 | 22 | GA | | | 7-11 | 29-22-11 | TB0080Y | C010 | BJ | | TB0046A | C003 | 2 | | 115-199 |
| 0242 | 22 | GA | | | 6-2 | 29-11-12 | M10557 | A | C | | D41704J | 1 | | | 115-199 |
| 0245 | 24 | GK | | | 5-3 | 27-51-31 | D41410J | 9 | | | TB0080Y | C001 | BJ | | 001-099 |
| 0245 | 22 | GA | | | 6-7 | 27-51-31 | D41410J | 9 | | | TB0080Y | C001 | BJ | | 115-199 |
| 0246 | 20 | GA | | | 4-11 | 26-22-21 | D41414J | 52 | | | TB0046Y | C007 | BJ | | 001-099 |
| 0247 | 20 | GA | | | 4-11 | 26-22-21 | D41414J | 51 | | | TB0046Y | A002 | BJ | | 001-099 |
| 0248 | 20 | GA | | | 5-7 | 26-22-21 | D41950J | 5 | | | TB0046Y | A002 | BJ | | 001-099 |
| 0249 | 20 | GA | | | 7-5 | 26-22-21 | D02424 | A1 | | | TB0046Y | C007 | BJ | | 001-099 |
| 0253 | 22 | GA | | | 7-4 | 29-22-11 | D42094J | 4 | | | M10145 | A | C | | 115-199 |
| 0254 | 22 | GA | | | 5-5 | 29-22-11 | D41414J | 3 | | | TB0046Y | A008 | BJ | | 115-199 |
| 0255 | 22 | GA | | | 5-5 | 29-22-11 | D41414J | 23 | | | TB0046Y | A008 | BJ | | 115-199 |
| 0256 | 22 | GA | | | 2-7 | 29-22-11 | D41414J | 24 | | | D42006J | 25 | | | 115-199 |
| 0264 | 22 | GA | | | 6-2 | 29-22-11 | D42094J | 3 | | | M10145 | A | C | | 001-099 |
| 0265 | 22 | GA | | | 6-2 | 29-22-11 | D42094J | 4 | | | M10146 | A | C | | 001-099 |
| 0266 | 22 | GA | | | 0-7 | 29-22-11 | M10145 | B | C | | M10146 | B | C | * | 001-099 |
| 0267 | 22 | GA | | | 6-2 | 29-22-11 | M10146 | B | C | | D42094J | 5 | | | 001-099 |
| 0268 | 18 | GA | | | 2-9 | 32-12-12 | D42006J | 16 | 18 | | D41096J | 2 | 18 | | 001-099 |
| 0268 | 18 | GA | | | 4-0 | 32-12-12 | D42006J | 16 | 18 | | D41096J | 2 | 18 | | 115-199 |
| 0269 | 18 | GA | | | 2-9 | 32-12-12 | D42006J | 31 | 18 | | D41096J | 7 | 18 | | 001-099 |
| 0269 | 18 | GA | | | 4-0 | 32-12-12 | D42006J | 17 | 18 | | D41096J | 7 | 18 | | 115-199 |
| 0270 | 24 | GK | | | 4-4 | 26-15-11 | D02424 | D3 | | | D41414J | 11 | | | 001-099 |
| 0271 | 24 | GK | | | 4-4 | 26-15-11 | D02424 | D2 | | | D41414J | 12 | | | 001-099 |
| 0401 | 24 | GK | | | 4-1 | 26-15-12 | D02422 | C | | | TB0046Y | C001 | BJ | | 001-099 |
| 0402 | 24 | GK | | | 1-8 | 26-15-12 | D02422 | B | | | D41096J | 6 | | | 001-099 |
| 0403 | 24 | GK | | | 2-2 | 26-15-12 | D02422 | A | | | D41414J | 19 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 0404 | 24 | | GK | | 4-1 | 26-15-12 | D02422 | F | | | TB0046Y | C001 | BJ | | 001-099 |
| 0405 | 14 | | HA | | 3-7 | 27-51-11 | K00360 | A1 | E | * | D41418J | 4 | | | 001-099 |
| 0406 | 14 | | HA | | 3-7 | 27-51-11 | K00360 | B1 | E | * | D41418J | 5 | | | 001-099 |
| 0407 | 14 | | HA | | 3-8 | 27-51-11 | K00360 | C1 | E | * | D41418J | 6 | | | 001-099 |
| 0408 | 14 | | HA | | 4-0 | 27-51-11 | K00360 | A2 | E | * | D41692J | 20 | | | 001-099 |
| 0409 | 14 | | HA | | 4-1 | 27-51-11 | K00360 | B2 | E | * | D41692J | 22 | | | 001-099 |
| 0410 | 14 | | HA | | 4-1 | 27-51-11 | K00360 | C2 | E | * | D41692J | 24 | | | 001-099 |
| 0411 | 14 | | HA | | 1-10 | 27-51-11 | K00360 | A2 | E | * | K00359 | A2 | E | | 001-099 |
| 0412 | 14 | | HA | | 1-11 | 27-51-11 | K00360 | C2 | E | * | K00359 | B2 | E | | 001-099 |
| 0413 | 14 | | HA | | 1-10 | 27-51-11 | K00360 | B2 | E | * | K00359 | C2 | E | | 001-099 |
| 0414 | 14 | | HA | | 2-1 | 27-51-11 | K00360 | A1 | E | * | K00359 | A1 | E | | 001-099 |
| 0415 | 14 | | HA | | 2-2 | 27-51-11 | K00360 | B1 | E | * | K00359 | B1 | E | | 001-099 |
| 0416 | 14 | | HA | | 2-2 | 27-51-11 | K00360 | C1 | E | * | K00359 | C1 | E | | 001-099 |
| 0417 | 24 | | GK | | 2-5 | 27-51-11 | K00360 | X1 | C | * | K00359 | X1 | C | | 001-099 |
| 0418 | 24 | | GK | | 4-6 | 27-51-11 | K00360 | X2 | C | | D41692J | 4 | | | 001-099 |
| 0419 | 24 | | GK | | 4-7 | 27-51-11 | K00360 | X1 | C | * | D41692J | 7 | | | 001-099 |
| 0420 | 24 | | GK | | 3-11 | 27-51-11 | K00359 | X2 | C | | D41692J | 5 | | | 001-099 |
| 0421 | 14 | | HA | | 3-3 | 27-81-11 | K10098 | A1 | E | * | D41418J | 1 | | | 001-099 |
| 0422 | 14 | | HA | | 3-2 | 27-81-11 | K10098 | B1 | E | * | D41418J | 2 | | | 001-099 |
| 0423 | 14 | | HA | | 3-2 | 27-81-11 | K10098 | C1 | E | * | D41418J | 3 | | | 001-099 |
| 0424 | 14 | | HA | | 3-9 | 27-81-11 | K10098 | A2 | E | * | D41692J | 18 | | | 001-099 |
| 0425 | 14 | | HA | | 3-9 | 27-81-11 | K10098 | B2 | E | * | D41692J | 16 | | | 001-099 |
| 0426 | 14 | | HA | | 3-9 | 27-81-11 | K10098 | C2 | E | * | D41692J | 14 | | | 001-099 |
| 0427 | 14 | | HA | | 1-4 | 27-81-11 | K10098 | B2 | E | * | K10097 | C2 | E | | 001-099 |
| 0428 | 14 | | HA | | 1-3 | 27-81-11 | K10098 | C2 | E | * | K10097 | B2 | E | | 001-099 |
| 0429 | 14 | | HA | | 1-3 | 27-81-11 | K10098 | A2 | E | * | K10097 | A2 | E | | 001-099 |
| 0430 | 14 | | HA | | 1-3 | 27-81-11 | K10098 | A1 | E | * | K10097 | A1 | E | | 001-099 |
| 0431 | 14 | | HA | | 1-4 | 27-81-11 | K10098 | B1 | E | * | K10097 | B1 | E | | 001-099 |
| 0432 | 14 | | HA | | 1-4 | 27-81-11 | K10098 | C1 | E | * | K10097 | C1 | E | | 001-099 |
| 0433 | 24 | | GK | | 1-5 | 27-81-11 | K10098 | X1 | C | * | K10097 | X1 | C | | 001-099 |
| 0434 | 24 | | GK | | 3-11 | 27-81-11 | K10098 | X2 | C | | D41692J | 2 | | | 001-099 |
| 0435 | 24 | | GK | | 3-9 | 27-81-11 | K10097 | X2 | C | | D41692J | 1 | | | 001-099 |
| 0436 | 22 | | GA | | 3-3 | 27-51-21 | K10098 | X1 | C | * | TB0046Y | C002 | BJ | | 001-099 |
| 0437 | 24 | | GK | | 5-11 | 33-42-11 | D41412J | 1 | | | TB0046Y | C008 | BJ | | 001-099 |
| 0438 | 24 | | GK | | 5-8 | 33-42-11 | D41718J | 31 | | | TB0046Y | C008 | BJ | | 001-099 |
| 0439 | 24 | | GK | | 3-11 | 33-42-11 | D05100 | X2 | | | D41412J | 2 | | | 001-099 |
| 0440 | 24 | | GK | | 5-4 | 33-42-11 | D05100 | X1 | | | TB0046Y | A011 | BJ | | 001-099 |
| 0441 | 24 | | GK | | 5-10 | 33-42-11 | D41412J | 3 | | | TB0046Y | A011 | BJ | | 001-099 |
| 0442 | 24 | | GK | | 5-2 | 33-42-11 | D05102 | X1 | | | TB0046Y | A011 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----------|-------|-------------|-------|------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | | 286N1230 | | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | |
| 0443 | 24 | GK | | | 5-4 | 33-42-11 | D05102 | X2 | | | TB0046Y | C008 | BJ | | 001-099 |
| 0444 | 20 | GA | | | 3-4 | 33-42-11 | D05102 | A2 | | | D41410J | 6 | | | 001-099 |
| 0445 | 20 | GA | | | 3-4 | 33-42-11 | D05102 | A1 | | | D41410J | 11 | | | 001-099 |
| 0446 | 20 | GA | | | 3-5 | 33-42-11 | D05100 | A2 | | | D41410J | 5 | | | 001-099 |
| 0447 | 20 | GA | | | 3-11 | 33-42-11 | D05100 | A1 | | | D41626J | 4 | | | 001-099 |
| 0448 | 20 | GA | | | 3-11 | 33-42-11 | D05100 | A3 | | | D41626J | 5 | | | 001-099 |
| 0449 | 20 | GA | | | 2-7 | 33-42-21 | D05102 | B1 | | | D41416J | 13 | | | 001-099 |
| 0450 | 20 | GA | | | 2-9 | 33-42-21 | D05102 | B2 | | | D41414J | 4 | | | 001-099 |
| 0451 | 24 | GK | | | 2-1 | 33-22-11 | D41424J | 11 | | | D41412J | 31 | | | 001-099 |
| 0452 | 20 | GA | | | 2-4 | 24-53-21 | T00124 | HV | E | | D41418J | 12 | | | 001-099 |
| 0453 | 14 | HA | | | 5-0 | 24-53-21 | T00124 | GND | E | | GD00459 | AC.. | E | | 001-099 |
| 0454 | 14 | HA | | | 2-4 | 24-53-21 | T00124 | LV | E | | D41418J | 11 | | | 001-099 |
| 0456 | 20 | GA | | | 1-9 | 33-43-11 | D41626J | 7 | | | D41412J | 18 | | | 001-099 |
| 0457 | 20 | GA | | | 4-0 | 33-44-21 | D41410J | 4 | | | D41626J | 8 | | | 001-099 |
| 0458 | 24 | GK | | | 3-9 | 27-51-11 | K00359 | 12 | C | * | D41692J | 17 | | | 001-099 |
| 0459 | 24 | GK | | | 2-0 | 27-51-11 | K00359 | 11 | C | | K00360 | 11 | C | * | 001-099 |
| 0460 | 24 | GK | | | 1-11 | 27-51-11 | K00359 | 12 | C | * | K00360 | 12 | C | | 001-099 |
| 0461 | 24 | GK | | | 4-10 | 27-51-11 | D41412J | 29 | | | K00360 | 11 | C | * | 001-099 |
| 0462 | 24 | GK | | | 4-7 | 27-81-11 | K10097 | 12 | C | * | D41412J | 26 | | | 001-099 |
| 0463 | 24 | GK | | | 1-4 | 27-81-11 | K10097 | 11 | C | * | K10098 | 11 | C | | 001-099 |
| 0464 | 24 | GK | | | 1-4 | 27-81-11 | K10097 | 12 | C | * | K10098 | 12 | C | | 001-099 |
| 0465 | 24 | GK | | | 4-3 | 27-81-11 | K10097 | 11 | C | * | D41692J | 19 | | | 001-099 |
| 0466 | 22 | GA | | | 2-0 | 29-11-11 | D41426J | 4 | | | D42006J | 18 | | | 001-099 |
| 0467 | 22 | GA | | | 3-2 | 29-11-11 | D41410J | 27 | | | D42006J | 19 | | | 001-099 |
| 0468 | 22 | GA | | | 2-0 | 29-11-11 | D41870J | 5 | | | D42006J | 20 | | | 001-099 |
| 0469 | 22 | GA | | | 2-0 | 29-11-11 | D41870J | 6 | | | D42006J | 21 | | | 001-099 |
| 0470 | 22 | GA | | | 2-0 | 29-11-11 | D41870J | 7 | | | D42006J | 22 | | | 001-099 |
| 0651 | 24 | GK | | | 4-4 | 26-15-12 | D02424 | C2 | | | D41414J | 14 | | | 001-099 |
| 0652 | 24 | GK | | | 4-4 | 26-15-12 | D02424 | C1 | | | D41414J | 13 | | | 001-099 |
| 0653 | 24 | GK | | | 1-10 | 26-15-12 | D02424 | B2 | | | TB0081Y | C001 | BJ | | 001-099 |
| 0654 | 24 | GK | | | 4-4 | 26-15-12 | D02424 | B1 | | | D41414J | 2 | | | 001-099 |
| 0655 | 20 | GA | | | 4-6 | 26-15-12 | D02424 | A2 | | | D41096J | 3 | | | 001-099 |
| 0656 | 24 | GK | | | 7-5 | 26-15-12 | D02424 | X1 | | | TB0046Y | A001 | BJ | | 001-099 |
| 0657 | 24 | GK | | | 1-10 | 26-15-12 | D02424 | X2 | | | TB0081Y | C001 | BJ | | 001-099 |
| 0658 | 24 | GK | | | 4-4 | 26-15-12 | D02424 | C3 | | | D41414J | 17 | | | 001-099 |
| 0659 | 24 | GK | | | 2-6 | 26-15-12 | D41096J | 1 | | | D41414J | 18 | | | 001-099 |
| 0660 | 24 | GK | | | 5-7 | 26-15-12 | D41950J | 3 | | | TB0046Y | C001 | BJ | | 001-099 |
| 0661 | 24 | GK | | | 5-7 | 26-15-12 | D41950J | 4 | | | TB0046Y | A001 | BJ | | 001-099 |
| 0662 | 24 | GK | | | 4-11 | 26-15-12 | D41414J | 1 | | | TB0046Y | A001 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1230 | 286N1230 | | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 0663 | 24 | | GK | | 4-1 | 26-15-12 | D41096J | 4 | | | | TB0081Y | C001 | BJ | | 001-099 |
| 0664 | 24 | | GK | | 4-11 | 26-15-12 | D41414J | 22 | | | | TB0046Y | C001 | BJ | | 001-099 |
| 0665 | 20 | | GA | | 2-8 | 28-22-11 | K00187 | C1 | D | * | | D41870J | 27 | | | 001-099 |
| 0666 | 20 | | GA | | 2-7 | 28-22-11 | K00187 | X1 | C | | | D41870J | 14 | | | 001-099 |
| 0668 | 18 | | GA | | 3-0 | 28-22-11 | K10011 | C1 | D | * | | D41870J | 28 | 18 | | 001-099 |
| 0669 | 20 | | GA | | 3-3 | 28-22-11 | K00190 | C1 | D | * | | D41870J | 29 | | | 001-099 |
| 0670 | 20 | | GA | | 1-5 | 28-22-11 | K00190 | X2 | C | | | GD00453 | AC.. | 2 | | 001-099 |
| 0671 | 24 | | GK | | 1-6 | 28-22-31 | D02064 | 6 | | | | TB0081Y | A003 | BJ | | 001-008 |
| 0671 | 24 | | GK | | 1-8 | 28-22-31 | D07736 | 13 | | | | TB0081Y | A003 | BJ | | 009-099 |
| 0672 | 24 | | GK | | 1-11 | 28-22-31 | D02064 | 8 | | | | GD00452 | DC.. | 2 | | 001-008 |
| 0672 | 20 | | GA | | 2-1 | 28-22-31 | D07736 | 1 | | | | GD00452 | DC.. | 2 | | 009-099 |
| 0673 | 20 | | GA | | 4-3 | 28-22-31 | D02064 | 7 | | | | D42006J | 3 | | | 001-008 |
| 0673 | 20 | | GA | | 4-3 | 28-22-31 | D07736 | 6 | | | | D41414J | 49 | | | 009-099 |
| 0674 | 24 | | GK | | 4-0 | 28-22-31 | D41414J | 7 | | | | TB0081Y | A003 | BJ | | 001-099 |
| 0675 | 24 | | GK | | 4-0 | 28-22-31 | D41414J | 6 | | | | TB0081Y | A003 | BJ | | 001-099 |
| 0676 | 22 | | GA | | 4-1 | 28-22-21 | D02140 | 7 | | | | D41426J | 3 | | | 001-099 |
| 0677 | 22 | | GA | | 4-4 | 28-22-21 | D02140 | 1 | | | | D42006J | 1 | | | 001-099 |
| 0678 | 22 | | GA | | 4-4 | 28-22-21 | D02140 | 6 | | | | D42006J | 2 | | | 001-099 |
| 0679 | 20 | | GA | | 2-0 | 28-22-21 | D02140 | 3 | | | | GD00452 | DC.. | 2 | | 001-099 |
| 0680 | 22 | | GA | | 4-2 | 28-22-21 | D02020 | 7 | | | | D41426J | 1 | | | 001-099 |
| 0681 | 22 | | GA | | 4-10 | 28-22-21 | D02020 | 1 | | | | D41950J | 1 | | | 001-099 |
| 0682 | 22 | | GA | | 4-10 | 28-22-21 | D02020 | 6 | | | | D41950J | 2 | | | 001-099 |
| 0683 | 22 | | GA | | 2-1 | 28-22-21 | D02020 | 3 | | | | GD00452 | DC.. | 2 | | 001-099 |
| 0684 | 20 | | GA | | 4-1 | 26-22-21 | TB0046Y | A002 | BJ | | | D41096J | 9 | | | 001-099 |
| 0685 | 20 | | GA | | 6-3 | 28-22-11 | K10011 | X1 | C | | | D11714 | A3 | | | ALL |
| 0686 | 18 | | GA | | 4-2 | 28-22-11 | D41410J | 21 | | | | TB0046G | 15 | 2 | | 001-099 |
| 0688 | 20 | | GA | | 5-11 | 26-22-21 | TB0046Y | C007 | BJ | | | D41414J | 15 | | | 001-099 |
| 0690 | 20 | | GA | | 6-7 | 26-22-21 | TB0046Y | A002 | BJ | | | D41950J | 6 | | | 001-099 |
| 0691 | 24 | | GK | | 4-3 | 28-22-31 | D02064 | 2 | | | | D42006J | 4 | | | 001-008 |
| 0692 | 24 | | GK | | 4-1 | 28-22-31 | D02064 | 5 | | | | D41414J | 8 | | | 001-008 |
| 0692 | 24 | | GK | | 4-3 | 28-22-31 | TB0081Y | C012 | BJ | | | D41414J | 8 | | | 009-099 |
| 0693 | 18 | | GA | | 2-10 | 28-22-11 | K00187 | X2 | C | | | GD00452 | AC.. | 2 | | 001-099 |
| 0694 | 18 | | GA | | 2-7 | 28-22-11 | K10011 | X2 | C | | | GD00452 | AC.. | 2 | | 001-099 |
| 0695 | 20 | | GA | | 3-2 | 28-22-11 | K00190 | X1 | C | | | D41870J | 15 | | | 001-099 |
| 0696 | 24 | | GK | | 3-7 | 30-31-11 | D02114 | D2 | | | | D41410J | 12 | | | 001-099 |
| 0697 | 24 | | GK | | 4-1 | 30-31-11 | D03300 | B2 | | | | D41870J | 12 | | | 001-099 |
| 0698 | 24 | | GK | | 2-0 | 30-31-11 | D03300 | B1 | | | | GD00453 | AC.. | 2 | | 001-099 |
| 0699 | 24 | | GK | | 2-4 | 30-31-11 | D02116 | X2 | | | | GD00452 | DC.. | 2 | | 001-099 |
| 0700 | 24 | | GK | | 1-9 | 30-32-11 | D02120 | B2 | | | | GD00453 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | | 286N1230 | | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | |
| 0701 | 22 | GA | | | 1-9 | 30-32-11 | D02120 | | B1 | | GD00453 | AC.. | 2 | | 001-099 |
| 0702 | 24 | GK | | | 3-3 | 30-32-11 | D02120 | | X1 | | D41414J | 53 | | | 001-099 |
| 0703 | 24 | GK | | | 4-6 | 30-32-11 | D41410J | | 31 | | TB0081Y | A004 | BJ | | 001-099 |
| 0704 | 24 | GK | | | 1-9 | 30-32-11 | D02120 | | D2 | | TB0081Y | A004 | BJ | | 001-099 |
| 0705 | 24 | GK | | | 3-8 | 30-32-11 | D41704J | | 20 | | TB0081Y | A004 | BJ | | 001-099 |
| 0706 | 24 | GK | | | 4-7 | 30-32-11 | D03300 | | X1 | | D41414J | 54 | | | 001-099 |
| 0707 | 24 | GK | | | 2-0 | 30-32-11 | D03300 | | X2 | | GD00453 | DC.. | 2 | | 001-099 |
| 0708 | 22 | GA | | | 3-10 | 30-32-11 | D02120 | | C1 | | D41410J | 10 | | | 001-099 |
| 0709 | 22 | GA | | | 2-0 | 30-32-11 | D03300 | | A1 | | TB0081Y | C004 | BJ | | 001-099 |
| 0710 | 22 | GA | | | 3-6 | 30-32-11 | D41870J | | 19 | | TB0081Y | C004 | BJ | | 001-099 |
| 0711 | 22 | GA | | | 4-1 | 30-32-11 | D41870J | | 20 | | D03300 | A2 | | | 001-099 |
| 0712 | 22 | GA | | | 3-8 | 34-12-12 | D02116 | | A2 | | D41410J | 7 | | | 001-099 |
| 0713 | 22 | GA | | | 3-10 | 34-12-12 | D02120 | | D3 | | D41410J | 8 | | | 001-099 |
| 0714 | 24 | GK | | | 1-9 | 30-32-11 | D02120 | | X2 | | GD00453 | DC.. | 2 | | 001-099 |
| 0715 | 24 | GK | | | 2-0 | 30-31-11 | D02114 | | X2 | | GD00453 | DC.. | 2 | | 001-099 |
| 0716 | 24 | GK | | | 2-7 | 30-31-11 | D02114 | | B1 | | D41870J | 16 | | | 001-099 |
| 0717 | 24 | GK | | | 2-0 | 30-31-11 | D02114 | | C3 | | GD00453 | DC.. | 2 | | 001-099 |
| 0718 | 24 | GK | | | 2-0 | 30-31-11 | D02114 | | B2 | | GD00453 | DC.. | 2 | | 001-099 |
| 0719 | 24 | GK | | | 1-11 | 30-31-11 | D02116 | | X1 | | TB0081Y | A002 | BJ | | 001-099 |
| 0720 | 24 | GK | | | 2-0 | 30-31-11 | D02114 | | X1 | | TB0081Y | A002 | BJ | | 001-099 |
| 0721 | 24 | GK | | | 3-11 | 30-31-11 | D41426J | | 5 | | TB0081Y | A002 | BJ | | 001-099 |
| 0722 | 24 | GK | | | 2-5 | 30-31-11 | D41416J | | 4 | | D42030J | 1 | | | 001-099 |
| 0723 | 24 | GK | | | 3-4 | 30-31-11 | D02116 | | C1 | | D42030J | 2 | | | 001-099 |
| 0724 | 24 | GK | | | 2-8 | 30-31-11 | D02116 | | B1 | | D41870J | 17 | | | 001-099 |
| 0725 | 24 | GK | | | 2-8 | 30-31-11 | D02116 | | D3 | | D41870J | 22 | | | 001-099 |
| 0726 | 24 | GK | | | 2-4 | 30-31-11 | D02116 | | B2 | | GD00452 | DC.. | 2 | | 001-099 |
| 0727 | 24 | GK | | | 2-4 | 30-31-11 | D02116 | | C3 | | GD00452 | DC.. | 2 | | 001-099 |
| 0728 | 24 | GK | | | 2-10 | 30-31-11 | D02116 | | A3 | | D41704J | 21 | | | 001-099 |
| 0729 | 24 | GK | | | 3-8 | 30-31-11 | D02116 | | D2 | | D41410J | 3 | | | 001-099 |
| 0730 | 24 | GK | | | 3-3 | 30-31-11 | D02114 | | C1 | | D42030J | 4 | | | 001-099 |
| 0731 | 24 | GK | | | 2-7 | 30-31-11 | D02114 | | D3 | | D41870J | 21 | | | 001-099 |
| 0732 | 24 | GK | | | 2-9 | 30-31-11 | D02114 | | A3 | | D41704J | 22 | | | 001-099 |
| 0733 | 20 | GA | | | 2-9 | 32-35-11 | D42006J | | 23 | | D41096J | 10 | | | 001-099 |
| 0734 | 20 | GA | | | 2-9 | 32-35-11 | D42006J | | 24 | | D41096J | 11 | | | 001-099 |
| 0735 | 20 | GA | | | 1-11 | 28-22-31 | D02064 | | 3 | | GD00452 | DC.. | 2 | | 001-008 |
| 0735 | 20 | GA | | | 2-1 | 28-22-31 | D07736 | | 3 | | GD00452 | DC.. | 2 | | 009-099 |
| 0736 | 20 | GA | | | 3-4 | 33-42-12 | D05102 | | C2 | | D41410J | 25 | | | 001-099 |
| 0737 | 20 | GA | | | 3-4 | 33-42-12 | D05102 | | C1 | | D41410J | 18 | | | 001-099 |
| 0738 | 20 | GA | | | 4-6 | 33-42-31 | D05576 | | A2 | | D41414J | 10 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 0741 | 20 | | GA | | 4-4 | 33-42-31 | D05576 | | A1 | | D41416J | | 16 | | 001-099 |
| 0742 | 24 | | GK | | 7-5 | 33-42-31 | D05576 | | X1 | | TB0046Y | A011 | BJ | | 001-099 |
| 0743 | 24 | | GK | | 8-7 | 33-42-31 | D05576 | | X2 | | TB0046Y | C008 | BJ | | 001-099 |
| 0746 | 24 | | GK | | 2-5 | 30-31-11 | D41416J | | 18 | | D42030J | | 3 | | 001-099 |
| 0755 | 20 | | GA | | 5-7 | 26-22-21 | TB0046Y | C007 | BJ | | D41950J | | 11 | | 001-099 |
| 0756 | 24 | | GK | | 1-11 | 28-22-31 | D07736 | | 5 | | TB0081Y | C012 | BJ | | 009-099 |
| 0757 | 20 | | GA | | 2-1 | 28-22-31 | D07736 | | 12 | | GD00452 | DC.. | 2 | | 009-099 |
| 0758 | 20 | | GA | | 4-3 | 28-22-31 | D07736 | | 14 | | D41414J | | 55 | | 009-099 |
| 0759 | 24 | | GK | | 1-11 | 28-22-31 | D07736 | | 7 | | TB0081Y | A013 | BJ | | 009-099 |
| 0760 | 24 | | GK | | 1-11 | 28-22-32 | D07738 | | 13 | | TB0081Y | A012 | BJ | | 009-099 |
| 0761 | 24 | | GK | | 5-3 | 28-22-32 | TB0081Y | A012 | BJ | | D41412J | | 36 | | 009-099 |
| 0762 | 24 | | GK | | 5-3 | 28-22-32 | TB0081Y | A012 | BJ | | D41412J | | 37 | | 009-099 |
| 0763 | 20 | | GA | | 2-1 | 28-22-32 | D07738 | | 1 | | GD00452 | DC.. | 2 | | 009-099 |
| 0764 | 20 | | GA | | 2-1 | 28-22-32 | D07738 | | 3 | | GD00452 | DC.. | 2 | | 009-099 |
| 0765 | 24 | | GK | | 1-11 | 28-22-32 | D07738 | | 5 | | TB0081Y | C012 | BJ | | 009-099 |
| 0766 | 20 | | GA | | 2-1 | 28-22-32 | D07738 | | 12 | | GD00452 | DC.. | 2 | | 009-099 |
| 0767 | 20 | | GA | | 5-3 | 28-22-32 | D07738 | | 6 | | D41412J | | 38 | | 009-099 |
| 0768 | 24 | | GK | | 5-3 | 28-22-32 | D07738 | | 14 | | D41412J | | 39 | | 009-099 |
| 0769 | 24 | | GK | | 1-11 | 28-22-32 | D07738 | | 7 | | TB0081Y | A013 | BJ | | 009-099 |
| 0770 | 24 | | GK | | 5-3 | 28-22-32 | TB0081Y | A013 | BJ | | D41412J | | 40 | | 009-099 |
| 0771 | 24 | | GK | | 5-3 | 28-22-32 | TB0081Y | A013 | BJ | | D41412J | | 41 | | 009-099 |
| 0829 | 20 | | GA | | 3-0 | 28-22-11 | D11716 | | A2 | | D41422J | | 12 | | ALL |
| 0831 | 20 | | GA | | 1-2 | 28-22-11 | D11716 | | A1 | | D11714 | | X1 | | ALL |
| 0832 | 20 | | GA | | 1-3 | 28-22-11 | D11716 | | X2 | | GD00451 | AC.. | 2 | | ALL |
| 0833 | 20 | | GA | | 4-5 | 28-22-11 | D41704J | | 24 | | TB0046B | A019 | 2 | | ALL |
| 0834 | 20 | | GA | | 7-8 | 28-22-11 | D11714 | | X2 | | TB0046B | A019 | 2 | | ALL |
| 0835 | 20 | | GA | | 4-3 | 28-22-11 | D41870J | | 9 | | TB0046B | C019 | 2 | | ALL |
| 0836 | 20 | | GA | | 7-8 | 28-22-11 | D11714 | | A2 | | TB0046G | | 15 | 2 | ALL |
| 0837 | 20 | | GA | | 7-7 | 28-22-11 | D11716 | | X1 | | TB0046G | | 15 | 2 | ALL |
| 0838 | 18 | | GA | | 4-3 | 28-22-11 | D41870J | | 13 | 18 | TB0046G | | 16 | 2 | 001-099 |
| 0869 | 18 | | GA | | 4-2 | 28-22-11 | D41410J | | 23 | | TB0046G | | 16 | 2 | 001-099 |
| 3001B | 18 | | HC | AA | 3-0 | 28-22-11 | D41416J | | 3 | | K00187 | C1 | D | * | 001-099 |
| 3001R | 18 | | HC | AA | 0-0 | 28-22-11 | D41416J | | 1 | | K00187 | A1 | D | | 001-099 |
| 3001Y | 18 | | HC | AA | 0-0 | 28-22-11 | D41416J | | 2 | | K00187 | B1 | D | | 001-099 |
| 3002B | 18 | | HC | AB | 2-9 | 28-22-11 | D41704J | | 23 | 18 | K00187 | C2 | D | | 001-099 |
| 3002R | 18 | | HC | AB | 0-0 | 28-22-11 | D41704J | | 25 | 18 | K00187 | A2 | D | | 001-099 |
| 3002Y | 18 | | HC | AB | 0-0 | 28-22-11 | D41704J | | 27 | 18 | K00187 | B2 | D | | 001-099 |
| 3003B | 16 | | GC | AC | 3-3 | 28-22-11 | D41416J | | 9 | | K10011 | C1 | D | * | 001-099 |
| 3003R | 16 | | GC | AC | 0-0 | 28-22-11 | D41416J | | 7 | | K10011 | A1 | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1230 | 286N1230 | | | INTERNAL P33 - PLATE D (continued) | | | | | | | | | | | |
| 3003Y | 16 | | GC | AC | 0-0 | 28-22-11 | D41416J | 8 | | | K10011 | B1 | D | | 001-099 |
| 3005B | 18 | | GC | AE | 3-6 | 28-22-11 | K00190 | C1 | D | * | D41416J | 12 | | | 001-099 |
| 3005R | 18 | | GC | AE | 0-0 | 28-22-11 | K00190 | A1 | D | | D41416J | 10 | | | 001-099 |
| 3005Y | 18 | | GC | AE | 0-0 | 28-22-11 | K00190 | B1 | D | | D41416J | 11 | | | 001-099 |
| 3006B | 18 | | GC | AF | 4-8 | 28-22-11 | K00190 | C2 | D | | D41722J | 3 | | | 001-099 |
| 3006R | 18 | | GC | AF | 0-0 | 28-22-11 | K00190 | A2 | D | | D41722J | 1 | | | 001-099 |
| 3006Y | 18 | | GC | AF | 0-0 | 28-22-11 | K00190 | B2 | D | | D41722J | 2 | | | 001-099 |
| 3507B | 16 | | VH | BA | 4-0 | 28-22-11 | K10011 | C2 | D | | K10875 | C2 | D | | ALL |
| 3507R | 16 | | VH | BA | 0-0 | 28-22-11 | K10011 | A2 | D | | K10875 | A2 | D | | ALL |
| 3507Y | 16 | | VH | BA | 0-0 | 28-22-11 | K10011 | B2 | D | | K10875 | B2 | D | | ALL |
| 3507Z | | | | BA | 0-0 | 28-22-11 | K10011 | DED | | | K10875 | DED | | | ALL |
| 3508B | 16 | | VH | BB | 4-0 | 28-22-11 | K10875 | C1 | D | | D41704J | 6 | | | ALL |
| 3508R | 16 | | VH | BB | 0-0 | 28-22-11 | K10875 | A1 | D | | D41704J | 4 | | | ALL |
| 3508Y | 16 | | VH | BB | 0-0 | 28-22-11 | K10875 | B1 | D | | D41704J | 10 | | | ALL |
| 3508Z | | | | BB | 0-0 | 28-22-11 | K10875 | DED | | | D41704J | DED | | | ALL |
| W1232 | 286N1232 | | | INTERNAL P33 - PLATE 'C' | | | | | | | | | | | |
| 0006 | 24 | | GK | | 4-3 | 26-15-12 | D02424 | C2 | | | D41414J | 14 | | | 115-199 |
| 0007 | 24 | | GK | | 4-3 | 26-15-12 | D02424 | C1 | | | D41414J | 13 | | | 115-199 |
| 0008 | 24 | | GK | | 1-11 | 26-15-12 | D02424 | B2 | | | TB0081Y | C001 | BJ | | 115-199 |
| 0009 | 24 | | GK | | 4-3 | 26-15-12 | D02424 | B1 | | | D41414J | 2 | | | 115-199 |
| 0010 | 20 | | GA | | 4-10 | 26-15-12 | D02424 | A2 | | | D41096J | 3 | | | 115-199 |
| 0011 | 24 | | GK | | 7-3 | 26-15-12 | D02424 | X1 | | | TB0046Y | A001 | BJ | | 115-199 |
| 0012 | 24 | | GK | | 1-11 | 26-15-12 | D02424 | X2 | | | TB0081Y | C001 | BJ | | 115-199 |
| 0013 | 24 | | GK | | 4-3 | 26-15-12 | D02424 | C3 | | | D41414J | 17 | | | 115-199 |
| 0014 | 24 | | GK | | 2-11 | 26-15-12 | D41414J | 18 | | | D41096J | 1 | | | 115-199 |
| 0016 | 24 | | GK | | 5-6 | 26-15-12 | D41950J | 3 | | | TB0046Y | C001 | BJ | | 115-199 |
| 0017 | 24 | | GK | | 5-6 | 26-15-12 | D41950J | 4 | | | TB0046Y | A001 | BJ | | 115-199 |
| 0018 | 24 | | GK | | 4-10 | 26-15-12 | D41414J | 1 | | | TB0046Y | A001 | BJ | | 115-199 |
| 0019 | 24 | | GK | | 4-7 | 26-15-12 | D41096J | 4 | | | TB0081Y | C001 | BJ | | 115-199 |
| 0020 | 24 | | GK | | 4-10 | 26-15-12 | D41414J | 22 | | | TB0046Y | C001 | BJ | | 115-199 |
| 0036 | 20 | | GA | | 2-6 | 28-22-11 | K00187 | C1 | D | * | D41870J | 27 | | | 115-199 |
| 0037 | 20 | | GA | | 2-5 | 28-22-11 | D41870J | 14 | | | K00187 | X1 | C | | 115-199 |
| 0038 | 18 | | GA | | 3-11 | 28-22-11 | D41870J | 13 | 18 | | TB0046G | 16 | 2 | | 115-199 |
| 0039 | 18 | | GA | | 2-10 | 28-22-11 | K10011 | C1 | D | * | D41870J | 28 | 18 | | 115-199 |
| 0040 | 20 | | GA | | 3-0 | 28-22-11 | D41870J | 29 | | | K00190 | C1 | D | * | 115-199 |
| 0041 | 20 | | GA | | 1-3 | 28-22-11 | K00190 | X2 | C | | GD00453 | AC.. | 2 | | 115-199 |
| 0050 | 24 | | GK | | 1-8 | 28-22-31 | D02064 | 6 | | | TB0081Y | A003 | BJ | | 115-199 |
| 0051 | 24 | | GK | | 2-0 | 28-22-31 | D02064 | 8 | | | GD00452 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1232 | 286N1232 | | | INTERNAL P33 - PLATE 'C' (continued) | | | | | | | | | | | |
| 0052 | 20 | | GA | | 2-0 | 28-22-31 | D02064 | | 3 | | GD00452 | DC.. | 2 | | 115-199 |
| 0053 | 20 | | GA | | 4-2 | 28-22-31 | D02064 | | 7 | | D42006J | | 3 | | 115-199 |
| 0054 | 24 | | GK | | 4-0 | 28-22-31 | D41414J | | 7 | | TB0081Y | A003 | BJ | | 115-199 |
| 0055 | 24 | | GK | | 4-0 | 28-22-31 | D41414J | | 6 | | TB0081Y | A003 | BJ | | 115-199 |
| 0057 | 22 | | GA | | 4-1 | 28-22-21 | D02140 | | 7 | | D41426J | | 3 | | 115-199 |
| 0058 | 22 | | GA | | 4-2 | 28-22-21 | D02140 | | 1 | | D42006J | | 1 | | 115-199 |
| 0059 | 22 | | GA | | 4-2 | 28-22-21 | D02140 | | 6 | | D42006J | | 2 | | 115-199 |
| 0060 | 22 | | GA | | 2-1 | 28-22-21 | D02140 | | 3 | | GD00452 | DC.. | 2 | | 115-199 |
| 0061 | 22 | | GA | | 4-1 | 28-22-21 | D02020 | | 7 | | D41426J | | 1 | | 115-199 |
| 0062 | 22 | | GA | | 4-9 | 28-22-21 | D02020 | | 1 | | D41950J | | 1 | | 115-199 |
| 0063 | 22 | | GA | | 4-9 | 28-22-21 | D02020 | | 6 | | D41950J | | 2 | | 115-199 |
| 0064 | 22 | | GA | | 2-1 | 28-22-21 | D02020 | | 3 | | GD00452 | DC.. | 2 | | 115-199 |
| 0065 | 20 | | GA | | 3-8 | 26-15-12 | D41950J | | 5 | | D41096J | | 9 | | 115-199 |
| 0067 | 18 | | GA | | 3-10 | 28-22-11 | D41410J | | 17 | 18 | TB0046G | | 15 | 2 | 115-199 |
| 0069 | 18 | | GA | | 3-10 | 28-22-11 | D41410J | | 18 | 18 | TB0046G | | 16 | 2 | 115-199 |
| 0070 | 24 | | GK | | 4-3 | 26-15-11 | D02424 | | D3 | | D41414J | | 11 | | 115-199 |
| 0071 | 24 | | GK | | 4-3 | 26-15-11 | D02424 | | D2 | | D41414J | | 12 | | 115-199 |
| 0073 | 20 | | GA | | 4-5 | 26-22-21 | D02424 | | A1 | | D42006J | | 9 | | 115-199 |
| 0074 | 24 | | GK | | 4-2 | 28-22-31 | D02064 | | 2 | | D42006J | | 4 | | 115-199 |
| 0075 | 24 | | GK | | 3-11 | 28-22-31 | D02064 | | 5 | | D41414J | | 8 | | 115-199 |
| 0076 | 18 | | GA | | 2-9 | 28-22-11 | K00187 | | X2 | C | GD00452 | AC.. | 2 | | 115-199 |
| 0077 | 18 | | GA | | 2-5 | 28-22-11 | K10011 | | X2 | C | GD00452 | AC.. | 2 | | 115-199 |
| 0078 | 20 | | GA | | 2-11 | 28-22-11 | K00190 | | X1 | C | D41870J | | 15 | | 115-199 |
| 0085 | 24 | | GK | | 3-6 | 30-31-11 | D02114 | | D2 | | D41410J | | 12 | | 115-199 |
| 0086 | 24 | | GK | | 3-10 | 30-31-11 | D03300 | | B2 | | D41870J | | 12 | | 115-199 |
| 0087 | 24 | | GK | | 1-10 | 30-31-11 | D03300 | | B1 | | GD00453 | AC.. | 2 | | 115-199 |
| 0088 | 24 | | GK | | 2-4 | 30-31-11 | D02116 | | X2 | | GD00452 | DC.. | 2 | | 115-199 |
| 0089 | 24 | | GK | | 1-8 | 30-32-11 | D02120 | | B2 | | GD00453 | DC.. | 2 | | 115-199 |
| 0090 | 22 | | GA | | 1-8 | 30-32-11 | D02120 | | B1 | | GD00453 | AC.. | 2 | | 115-199 |
| 0091 | 24 | | GK | | 3-3 | 30-32-11 | D02120 | | X1 | | D41414J | | 53 | | 115-199 |
| 0092 | 24 | | GK | | 4-7 | 30-32-11 | D41410J | | 31 | | TB0081Y | A004 | BJ | | 115-199 |
| 0093 | 24 | | GK | | 1-11 | 30-32-11 | D02120 | | D2 | | TB0081Y | A004 | BJ | | 115-199 |
| 0094 | 24 | | GK | | 3-6 | 30-32-11 | D41704J | | 20 | | TB0081Y | A004 | BJ | | 115-199 |
| 0095 | 24 | | GK | | 4-4 | 30-32-11 | D03300 | | X1 | | D41414J | | 54 | | 115-199 |
| 0096 | 24 | | GK | | 1-10 | 30-32-11 | D03300 | | X2 | | GD00453 | DC.. | 2 | | 115-199 |
| 0097 | 22 | | GA | | 3-10 | 30-32-11 | D02120 | | C1 | | D41410J | | 10 | | 115-199 |
| 0098 | 22 | | GA | | 2-1 | 30-32-11 | D03300 | | A1 | | TB0081Y | C004 | BJ | | 115-199 |
| 0099 | 22 | | GA | | 2-4 | 30-32-11 | D00592 | | C3 | | TB0081Y | C004 | BJ | | 115-199 |
| 0100 | 22 | | GA | | 3-5 | 30-32-11 | D41870J | | 19 | | TB0081Y | C004 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity | | | | | | | |
|------------|-------------|----|----|--------------------------------------|------|----------|----------|----|----|----|-----|-------|---------|---------|-------------|------|------|--------|-------|------|---------|--------|
| | | | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | | Term | Type | Splice | Equip | Term | Type | Splice |
| W1232 | 286N1232 | | | INTERNAL P33 - PLATE 'C' (continued) | | | | | | | | | | | | | | | | | | |
| 0101 | 22 | GA | | | 2-1 | 30-32-11 | D03300 | | | | A2 | | | TB0081Y | C002 | BJ | | | | | 115-199 | |
| 0102 | 22 | GA | | | 2-4 | 30-32-11 | D00592 | | | | C2 | | | TB0081Y | C002 | BJ | | | | | 115-199 | |
| 0103 | 22 | GA | | | 3-5 | 30-32-11 | D41870J | | | | 20 | | | TB0081Y | C002 | BJ | | | | | 115-199 | |
| 0104 | 22 | GA | | | 3-4 | 32-09-11 | D00592 | | | | X1 | | | D41410J | 15 | | | | | | 115-199 | |
| 0105 | 22 | GA | | | 2-4 | 32-09-11 | D00592 | | | | X2 | | | D41704J | 29 | | | | | | 115-199 | |
| 0106 | 24 | GK | | | 3-8 | 34-12-12 | D02116 | | | | A2 | | | D41410J | 7 | | | | | | 115-199 | |
| 0107 | 24 | GK | | | 3-10 | 34-12-12 | D02120 | | | | D3 | | | D41410J | 8 | | | | | | 115-199 | |
| 0109 | 24 | GK | | | 1-8 | 30-32-11 | D02120 | | | | X2 | | | GD00453 | DC.. | 2 | | | | | 115-199 | |
| 0113 | 24 | GK | | | 1-11 | 30-31-11 | D02114 | | | | X2 | | | GD00453 | DC.. | 2 | | | | | 115-199 | |
| 0114 | 24 | GK | | | 2-5 | 30-31-11 | D02114 | | | | B1 | | | D41870J | 16 | | | | | | 115-199 | |
| 0115 | 24 | GK | | | 1-11 | 30-31-11 | D02114 | | | | C3 | | | GD00453 | DC.. | 2 | | | | | 115-199 | |
| 0116 | 24 | GK | | | 1-11 | 30-31-11 | D02114 | | | | B2 | | | GD00453 | DC.. | 2 | | | | | 115-199 | |
| 0117 | 24 | GK | | | 2-0 | 30-31-11 | D02116 | | | | X1 | | | TB0081Y | A002 | BJ | | | | | 115-199 | |
| 0118 | 24 | GK | | | 2-1 | 30-31-11 | D02114 | | | | X1 | | | TB0081Y | A002 | BJ | | | | | 115-199 | |
| 0119 | 24 | GK | | | 4-0 | 30-31-11 | D41426J | | | | 18 | | | TB0081Y | A002 | BJ | | | | | 115-199 | |
| 0120 | 24 | GK | | | 2-8 | 30-31-11 | D41416J | | | | 4 | | | D42030J | 1 | | | | | | 115-199 | |
| 0121 | 24 | GK | | | 3-6 | 30-31-11 | D02116 | | | | C1 | | | D42030J | 2 | | | | | | 115-199 | |
| 0122 | 24 | GK | | | 2-6 | 30-31-11 | D02116 | | | | B1 | | | D41870J | 17 | | | | | | 115-199 | |
| 0123 | 24 | GK | | | 2-6 | 30-31-11 | D02116 | | | | D3 | | | D41870J | 22 | | | | | | 115-199 | |
| 0124 | 24 | GK | | | 2-4 | 30-31-11 | D02116 | | | | B2 | | | GD00452 | DC.. | 2 | | | | | 115-199 | |
| 0125 | 24 | GK | | | 2-4 | 30-31-11 | D02116 | | | | C3 | | | GD00452 | DC.. | 2 | | | | | 115-199 | |
| 0126 | 24 | GK | | | 2-7 | 30-31-11 | D02116 | | | | A3 | | | D41704J | 21 | | | | | | 115-199 | |
| 0127 | 24 | GK | | | 3-8 | 30-31-11 | D02116 | | | | D2 | | | D41410J | 3 | | | | | | 115-199 | |
| 0128 | 24 | GK | | | 2-5 | 30-31-11 | D02114 | | | | C1 | | | D41870J | 18 | | | | | | 115-199 | |
| 0129 | 24 | GK | | | 2-5 | 30-31-11 | D02114 | | | | D3 | | | D41870J | 21 | | | | | | 115-199 | |
| 0130 | 24 | GK | | | 2-6 | 30-31-11 | D02114 | | | | A3 | | | D41704J | 22 | | | | | | 115-199 | |
| 0145 | 20 | GA | | | 3-2 | 32-35-11 | D42006J | | | | 23 | | | D41096J | 10 | | | | | | 115-199 | |
| 0146 | 20 | GA | | | 3-2 | 32-35-11 | D42006J | | | | 24 | | | D41096J | 11 | | | | | | 115-199 | |
| 3001B | 18 | HC | AA | | 2-11 | 28-22-11 | D41416J | | | | 3 | | | K00187 | C1 | D | | * | | | 115-199 | |
| 3001R | 18 | HC | AA | | 0-0 | 28-22-11 | D41416J | | | | 1 | | | K00187 | A1 | D | | | | | 115-199 | |
| 3001Y | 18 | HC | AA | | 0-0 | 28-22-11 | D41416J | | | | 2 | | | K00187 | B1 | D | | | | | 115-199 | |
| 3002B | 18 | HC | AB | | 2-7 | 28-22-11 | D41704J | | | | 23 | 18 | | K00187 | C2 | D | | | | | 115-199 | |
| 3002R | 18 | HC | AB | | 0-0 | 28-22-11 | D41704J | | | | 25 | 18 | | K00187 | A2 | D | | | | | 115-199 | |
| 3002Y | 18 | HC | AB | | 0-0 | 28-22-11 | D41704J | | | | 27 | 18 | | K00187 | B2 | D | | | | | 115-199 | |
| 3003B | 16 | GC | AC | | 3-2 | 28-22-11 | D41416J | | | | 9 | | | K10011 | C1 | D | | * | | | 115-199 | |
| 3003R | 16 | GC | AC | | 0-0 | 28-22-11 | D41416J | | | | 7 | | | K10011 | A1 | D | | | | | 115-199 | |
| 3003Y | 16 | GC | AC | | 0-0 | 28-22-11 | D41416J | | | | 8 | | | K10011 | B1 | D | | | | | 115-199 | |
| 3005B | 18 | HC | AE | | 3-5 | 28-22-11 | K00190 | | | | C1 | D | * | D41416J | 12 | | | | | | 115-199 | |
| 3005R | 18 | HC | AE | | 0-0 | 28-22-11 | K00190 | | | | A1 | D | | D41416J | 10 | | | | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1232 | 286N1232 | | | INTERNAL P33 - PLATE 'C' (continued) | | | | | | | | | | | |
| 3005Y | 18 | HC | AE | | 0-0 | 28-22-11 | K00190 | B1 | D | | D41416J | 11 | | | 115-199 |
| 3006B | 18 | HC | AF | | 4-7 | 28-22-11 | K00190 | C2 | D | | D41722J | 3 | | | 115-199 |
| 3006R | 18 | HC | AF | | 0-0 | 28-22-11 | K00190 | A2 | D | | D41722J | 1 | | | 115-199 |
| 3006Y | 18 | HC | AF | | 0-0 | 28-22-11 | K00190 | B2 | D | | D41722J | 2 | | | 115-199 |
| W1234 | 286N1234 | | | INTERNAL P33 - PLATES 'A & B' | | | | | | | | | | | |
| 0001 | 24 | GK | | | 5-0 | 26-15-12 | D02422 | C | | | TB0046Y | C001 | BJ | | 115-199 |
| 0002 | 24 | GK | | | 2-0 | 26-15-12 | D02422 | B | | | D41096J | 6 | | | 115-199 |
| 0003 | 24 | GK | | | 2-7 | 26-15-12 | D02422 | A | | | D41414J | 19 | | | 115-199 |
| 0004 | 24 | GK | | | 5-0 | 26-15-12 | D02422 | F | | | TB0046Y | C001 | BJ | | 115-199 |
| 0006 | 14 | HA | | | 3-10 | 27-51-11 | K00360 | A1 | E | * | D41418J | 4 | | | 115-199 |
| 0007 | 14 | HA | | | 3-11 | 27-51-11 | K00360 | B1 | E | * | D41418J | 5 | | | 115-199 |
| 0008 | 14 | HA | | | 4-0 | 27-51-11 | K00360 | C1 | E | * | D41418J | 6 | | | 115-199 |
| 0009 | 14 | HA | | | 4-4 | 27-51-11 | K00360 | A2 | E | * | D41692J | 20 | | | 115-199 |
| 0010 | 14 | HA | | | 4-5 | 27-51-11 | K00360 | B2 | E | * | D41692J | 22 | | | 115-199 |
| 0011 | 14 | HA | | | 4-6 | 27-51-11 | K00360 | C2 | E | * | D41692J | 24 | | | 115-199 |
| 0012 | 14 | HA | | | 2-2 | 27-51-11 | K00360 | A2 | E | * | K00359 | A2 | E | | 115-199 |
| 0013 | 14 | HA | | | 2-3 | 27-51-11 | K00360 | C2 | E | * | K00359 | B2 | E | | 115-199 |
| 0014 | 14 | HA | | | 2-1 | 27-51-11 | K00360 | B2 | E | * | K00359 | C2 | E | | 115-199 |
| 0015 | 14 | HA | | | 2-7 | 27-51-11 | K00360 | A1 | E | * | K00359 | A1 | E | | 115-199 |
| 0016 | 14 | HA | | | 2-7 | 27-51-11 | K00360 | B1 | E | * | K00359 | B1 | E | | 115-199 |
| 0017 | 14 | HA | | | 2-7 | 27-51-11 | K00360 | C1 | E | * | K00359 | C1 | E | | 115-199 |
| 0018 | 24 | GK | | | 2-8 | 27-51-11 | K00359 | X1 | C | | K00360 | X1 | C | * | 115-199 |
| 0019 | 24 | GK | | | 4-9 | 27-51-11 | K00360 | X2 | C | | D41692J | 4 | | | 115-199 |
| 0020 | 24 | GK | | | 4-10 | 27-51-11 | K00360 | X1 | C | * | D41692J | 7 | | | 115-199 |
| 0021 | 24 | GK | | | 3-10 | 27-51-11 | K00359 | X2 | C | | D41692J | 5 | | | 115-199 |
| 0022 | 14 | HA | | | 3-5 | 27-81-11 | K10098 | A1 | E | * | D41418J | 1 | | | 115-199 |
| 0023 | 14 | HA | | | 3-4 | 27-81-11 | K10098 | B1 | E | * | D41418J | 2 | | | 115-199 |
| 0024 | 14 | HA | | | 3-4 | 27-81-11 | K10098 | C1 | E | * | D41418J | 3 | | | 115-199 |
| 0025 | 14 | HA | | | 4-1 | 27-81-11 | K10098 | A2 | E | * | D41692J | 18 | | | 115-199 |
| 0026 | 14 | HA | | | 4-1 | 27-81-11 | K10098 | B2 | E | * | D41692J | 16 | | | 115-199 |
| 0027 | 14 | HA | | | 4-0 | 27-81-11 | K10098 | C2 | E | * | D41692J | 14 | | | 115-199 |
| 0028 | 14 | HA | | | 1-3 | 27-81-11 | K10098 | B2 | E | * | K10097 | C2 | E | | 115-199 |
| 0029 | 14 | HA | | | 1-2 | 27-81-11 | K10098 | C2 | E | * | K10097 | B2 | E | | 115-199 |
| 0030 | 14 | HA | | | 1-3 | 27-81-11 | K10098 | A2 | E | * | K10097 | A2 | E | | 115-199 |
| 0031 | 14 | HA | | | 1-3 | 27-81-11 | K10098 | A1 | E | * | K10097 | A1 | E | | 115-199 |
| 0032 | 14 | HA | | | 1-3 | 27-81-11 | K10098 | B1 | E | * | K10097 | B1 | E | | 115-199 |
| 0033 | 14 | HA | | | 1-4 | 27-81-11 | K10098 | C1 | E | * | K10097 | C1 | E | | 115-199 |
| 0034 | 22 | GA | | | 1-4 | 27-81-11 | K10098 | X1 | C | * | K10097 | X1 | C | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W1234 | 286N1234 | | | INTERNAL P33 - PLATES 'A & B' (continued) | | | | | | | | | | | |
| 0035 | 22 | GA | | | 4-4 | 27-81-11 | K10098 | X2 | C | | D41692J | 2 | | | 115-199 |
| 0036 | 22 | GA | | | 4-1 | 27-81-11 | K10097 | X2 | C | | D41692J | 1 | | | 115-199 |
| 0037 | 22 | GA | | | 6-0 | 27-51-21 | K10098 | X1 | C | * | TB0046Y | C002 | BJ | | 115-199 |
| 0038 | 20 | GA | | | 5-0 | 33-42-11 | D41412J | | 1 | | TB0046Y | C008 | BJ | | 115-199 |
| 0039 | 20 | GA | | | 6-0 | 33-42-11 | D41718J | | 31 | | TB0046Y | C008 | BJ | | 115-199 |
| 0040 | 20 | GA | | | 3-3 | 33-42-11 | D05100 | X2 | | | D41412J | 2 | | | 115-199 |
| 0041 | 20 | GA | | | 5-4 | 33-42-11 | D05100 | X1 | | | TB0046Y | A011 | BJ | | 115-199 |
| 0042 | 20 | GA | | | 4-1 | 33-42-11 | D41412J | | 3 | | TB0046Y | A011 | BJ | | 115-199 |
| 0043 | 20 | GA | | | 7-5 | 33-42-11 | D05102 | X1 | | | TB0046Y | A011 | BJ | | 115-199 |
| 0044 | 20 | GA | | | 7-0 | 33-42-11 | D05102 | X2 | | | TB0046Y | C008 | BJ | | 115-199 |
| 0045 | 20 | GA | | | 5-5 | 33-42-11 | D05102 | A2 | | | D41410J | 6 | | | 115-199 |
| 0046 | 20 | GA | | | 5-5 | 33-42-11 | D05102 | A1 | | | D41410J | 11 | | | 115-199 |
| 0047 | 20 | GA | | | 3-10 | 33-42-11 | D05100 | A2 | | | D41410J | 5 | | | 115-199 |
| 0048 | 20 | GA | | | 3-11 | 33-42-11 | D05100 | A1 | | | D41626J | 4 | | | 115-199 |
| 0049 | 20 | GA | | | 3-11 | 33-42-11 | D05100 | A3 | | | D41626J | 5 | | | 115-199 |
| 0050 | 18 | GA | | | 4-4 | 33-42-21 | D05102 | B1 | | | D41416J | 13 | | | 115-199 |
| 0051 | 20 | GA | | | 4-9 | 33-42-21 | D05102 | B2 | | | D41414J | 4 | | | 115-199 |
| 0054 | 22 | GA | | | 3-3 | 33-22-11 | D41424J | | 10 | | D41412J | 31 | | | 115-199 |
| 0055 | 20 | GA | | | 2-6 | 24-53-21 | T00124 | HV | E | | D41418J | 12 | | | 115-199 |
| 0056 | 14 | HA | | | 5-3 | 24-53-21 | T00124 | GND | E | | GD00459 | AC.. | E | | 115-199 |
| 0057 | 14 | HA | | | 2-6 | 24-53-21 | T00124 | LV | E | | D41418J | 11 | | | 115-199 |
| 0059 | 20 | GA | | | 3-7 | 33-43-11 | D41626J | | 7 | | D41412J | 18 | | | 115-199 |
| 0060 | 20 | GA | | | 4-2 | 33-44-21 | D41410J | | 4 | | D41626J | 8 | | | 115-199 |
| 0080 | 22 | GA | | | 3-8 | 27-51-11 | K00359 | 12 | C | * | D41692J | 17 | | | 115-199 |
| 0081 | 22 | GA | | | 3-0 | 27-51-11 | K00359 | 11 | C | | K00360 | 11 | C | * | 115-199 |
| 0082 | 22 | GA | | | 3-0 | 27-51-11 | K00359 | 12 | C | * | K00360 | 12 | C | | 115-199 |
| 0083 | 22 | GA | | | 3-11 | 27-51-11 | D41412J | 29 | | | K00360 | 11 | C | * | 115-199 |
| 0084 | 22 | GA | | | 3-0 | 27-81-11 | K10097 | 12 | C | * | D41412J | 26 | | | 115-199 |
| 0085 | 22 | GA | | | 1-4 | 27-81-11 | K10097 | 11 | C | * | K10098 | 11 | C | | 115-199 |
| 0086 | 22 | GA | | | 1-4 | 27-81-11 | K10097 | 12 | C | * | K10098 | 12 | C | | 115-199 |
| 0087 | 22 | GA | | | 4-6 | 27-81-11 | K10097 | 11 | C | * | D41692J | 19 | | | 115-199 |
| 0088 | 22 | GA | | | 2-8 | 29-11-11 | D41426J | 4 | | | D42006J | 18 | | | 115-199 |
| 0089 | 22 | GA | | | 3-8 | 29-11-11 | D41410J | 27 | | | D42006J | 19 | | | 115-199 |
| 0090 | 22 | GA | | | 2-10 | 29-11-11 | D41870J | 5 | | | D42006J | 20 | | | 115-199 |
| 0091 | 22 | GA | | | 2-10 | 29-11-11 | D41870J | 6 | | | D42006J | 21 | | | 115-199 |
| 0092 | 22 | GA | | | 2-10 | 29-11-11 | D41870J | 7 | | | D42006J | 22 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1230

Page 18 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1240 | 286N1240 | | | INTERNAL P34 - PLATE COMPONENTS | | | | | | | | | | | |
| 0001 | 16 | | GK | | 4-0 | 33-21-11 | D02828 | | B2 | | D41476J | | 8 | | 001-099 |
| 0001 | 16 | | GK | | 2-0 | 33-21-11 | D41476J | | 8 | | D02828 | | B2 | | 115-199 |
| 0002 | 16 | | GK | | 4-0 | 33-21-11 | D02828 | | A2 | | D41476J | | 9 | | 001-099 |
| 0002 | 16 | | GK | | 2-0 | 33-21-11 | D41476J | | 9 | | D02828 | | A2 | | 115-199 |
| 0003 | 16 | | GK | | 3-0 | 33-21-11 | D02828 | | B1 | | T10003 | | LV | E | 001-099 |
| 0003 | 16 | | GK | | 2-0 | 33-21-11 | TB0047F | A002 | 2 | | D02828 | | B1 | | 115-199 |
| 0004 | 16 | | GK | | 4-0 | 33-21-11 | D02828 | | A1 | | T10004 | | LV | E | 001-099 |
| 0004 | 16 | | GK | | 2-0 | 33-21-11 | TB0047F | C002 | 2 | | D02828 | | A1 | | 115-199 |
| 0005 | 24 | | GK | | 3-0 | 33-21-11 | D02828 | | X2 | | GD01170 | AC.. | 2 | | 001-099 |
| 0005 | 24 | | GK | | 3-0 | 33-21-11 | GD01170 | AC.. | 2 | | D02828 | | X2 | | 115-199 |
| 0006 | 24 | | GK | | 4-0 | 33-21-11 | D02828 | | X1 | | D41474J | | 13 | | 001-099 |
| 0006 | 24 | | GK | | 3-0 | 33-21-11 | D41474J | | 13 | | D02828 | | X1 | | 115-199 |
| 0007 | 16 | | GK | | 4-0 | 33-21-31 | D02898 | | A3 | | D41476J | | 12 | | 001-099 |
| 0007 | 16 | | GK | | 3-0 | 33-21-31 | D02898 | | A3 | | D41476J | | 12 | | 115-199 |
| 0008 | 16 | | GK | | 4-0 | 33-21-31 | D02898 | | B3 | | D41476J | | 13 | | 001-099 |
| 0008 | 16 | | GK | | 3-0 | 33-21-31 | D02898 | | B3 | | D41476J | | 13 | | 115-199 |
| 0009 | 16 | | GK | | 3-0 | 33-21-31 | D02898 | | A1 | | TB0047G | | 2 | 2 | 001-099 |
| 0009 | 16 | | GK | | 3-0 | 33-21-31 | D02898 | | A1 | | TB0047G | | 27 | 2 | 115-199 |
| 0010 | 16 | | GK | | 3-0 | 33-21-31 | D02898 | | X1 | | TB0047G | | 2 | 2 | 001-099 |
| 0010 | 16 | | GK | | 3-0 | 33-21-31 | D02898 | | X1 | | TB0047G | | 27 | 2 | 115-199 |
| 0011 | 16 | | GK | | 3-0 | 33-21-31 | D02898 | | B1 | | TB0047F | A025 | 2 | | ALL |
| 0012 | 18 | | GK | | 3-0 | 33-21-31 | D02898 | | X2 | | GD01170 | AC.. | 2 | | ALL |
| 0013 | 16 | | GK | | 2-0 | 33-21-31 | D02898 | | A2 | | D02940 | | A1 | | ALL |
| 0014 | 16 | | GK | | 2-0 | 33-21-31 | D02898 | | B2 | | D02940 | | B1 | | ALL |
| 0015 | 16 | | GK | | 4-0 | 33-21-31 | D02940 | | A2 | | D40474J | | 1 | 16 | 001-099 |
| 0015 | 16 | | GK | | 3-0 | 33-21-31 | D02940 | | A2 | | D40474J | | 1 | 16 | 115-199 |
| 0016 | 16 | | GK | | 4-0 | 33-21-31 | D02940 | | B2 | | D40374J | | 1 | 16 | 001-099 |
| 0016 | 16 | | GK | | 3-0 | 33-21-31 | D02940 | | B2 | | D40374J | | 1 | 16 | 115-199 |
| 0017 | 24 | | GK | | 4-0 | 33-21-31 | D41474J | | 7 | | D02940 | | X1 | | 001-099 |
| 0017 | 24 | | GK | | 4-0 | 33-21-31 | D02940 | | X1 | | D41474J | | 7 | | 115-199 |
| 0018 | 24 | | GK | | 3-0 | 33-21-31 | GD01170 | AC.. | 2 | | D02940 | | X2 | | 001-099 |
| 0018 | 24 | | GK | | 3-0 | 33-21-31 | D02940 | | X2 | | GD01170 | AC.. | 2 | | 115-199 |
| 0019 | 20 | | GK | | 4-0 | 33-22-11 | TB0047Y | C029 | BJ | | D41474J | | 1 | | 001-099 |
| 0019 | 20 | | GK | | 5-0 | 33-22-11 | TB0047Y | C029 | BJ | | D41474J | | 1 | | 115-199 |
| 0020 | 22 | | GK | | 4-0 | 33-22-11 | TB0047Y | A014 | BJ | | D41474J | | 5 | | ALL |
| 0021 | 22 | | GK | | 5-0 | 33-22-11 | D41472J | | 43 | | TB0047Y | A014 | BJ | | 001-099 |
| 0021 | 22 | | GK | | 3-0 | 33-22-11 | D41472J | | 43 | | TB0047Y | A014 | BJ | | 115-199 |
| 0022 | 22 | | GK | | 4-0 | 33-22-11 | TB0047Z | | 10 | BJ | D41474J | | 3 | | 115-199 |
| 0023 | 22 | | GK | | 2-0 | 33-22-11 | D03082 | | B2 | | TB0047Y | A014 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1240

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1240 | 286N1240 | | | INTERNAL P34 - PLATE COMPONENTS (continued) | | | | | | | | | | | | |
| 0026 | 24 | | GK | | 2-0 | 33-22-11 | D03082 | | X1 | | | D03080 | | A3 | | 001-099 |
| 0026 | 22 | | GK | | 2-0 | 33-22-11 | D03082 | | X1 | | | D03080 | | A3 | | 115-199 |
| 0027 | 24 | | GK | | 2-0 | 33-22-11 | TB0047Y | | A028 | BJ | | D03080 | | A2 | | 001-099 |
| 0027 | 22 | | GK | | 3-0 | 33-22-11 | TB0047Y | | A028 | BJ | | D03080 | | A2 | | 115-199 |
| 0029 | 24 | | GK | | 3-0 | 33-22-11 | D03080 | | X2 | | | D41472J | | 16 | | 001-099 |
| 0029 | 22 | | GK | | 2-0 | 33-22-11 | D03080 | | X2 | | | D41472J | | 16 | | 115-199 |
| 0030 | 24 | | GK | | 2-0 | 33-22-11 | D03080 | | X1 | | | TB0047Y | | A028 | BJ | 001-099 |
| 0030 | 22 | | GK | | 3-0 | 33-22-11 | D03080 | | X1 | | | TB0047Y | | A028 | BJ | 115-199 |
| 0031 | 22 | | GK | | 3-0 | 52-51-11 | D03080 | | B3 | | | GD01170 | | DC.. | 2 | ALL |
| 0032 | 22 | | GK | | 3-0 | 52-51-11 | D03080 | | B2 | | | D41470J | | 33 | | 001-099 |
| 0032 | 22 | | GK | | 2-0 | 52-51-11 | D03080 | | B2 | | | D41470J | | 33 | | 115-199 |
| 0034 | 22 | | GK | | 4-0 | 33-22-12 | D41474J | | 2 | | | TB0047Z | | 7 | BJ | ALL |
| 0035 | 20 | | GK | | 3-0 | 33-22-13 | D41472J | | 10 | | | TB0047Z | | 7 | BJ | 115-199 |
| 0036 | 22 | | GK | | 4-0 | 33-22-14 | D41474J | | 21 | | | TB0047Z | | 7 | BJ | ALL |
| 0037 | 18 | | GK | | 3-0 | 33-24-11 | K10028 | | B2 | D | | TB0047F | | C001 | 2 | 001-099 |
| 0037 | 20 | | GK | | 3-0 | 33-24-11 | TB0047X | | B006 | BJ | | K10028 | | B2 | D | 115-199 |
| 0038 | 18 | | GK | | 3-0 | 33-24-11 | K10028 | | A2 | D | | TB0047F | | A001 | 2 | 001-099 |
| 0038 | 20 | | GK | | 2-0 | 33-24-11 | TB0047Y | | C011 | BJ | | K10028 | | A2 | D | 115-199 |
| 0039 | 24 | | GK | | 4-0 | 33-24-11 | TB0047Y | | C028 | BJ | | D41848J | | 13 | | 001-099 |
| 0039 | 22 | | GK | | 4-0 | 33-24-11 | D41848J | | 13 | | | TB0047Y | | C028 | BJ | 115-199 |
| 0040 | 18 | | GK | | 4-0 | 33-24-11 | K10028 | | A1 | D | * | D41476J | | 15 | | 001-099 |
| 0040 | 20 | | GK | | 2-0 | 33-24-11 | TB0047Y | | A012 | BJ | | K10028 | | A1 | D | 115-199 |
| 0041 | 18 | | GK | | 4-0 | 33-24-11 | K10028 | | B1 | D | | D41476J | | 14 | | 001-099 |
| 0041 | 18 | | GK | | 3-0 | 33-24-11 | D41472J | | 18 | 18 | | K10028 | | B1 | D | 115-199 |
| 0042 | 22 | | GK | | 4-0 | 33-24-11 | D02712 | | B1 | | | D41472J | | 19 | | 001-099 |
| 0042 | 22 | | GK | | 2-0 | 33-24-11 | D02712 | | B1 | | | D41472J | | 19 | | 115-199 |
| 0043 | 20 | | GK | | 3-0 | 33-24-11 | TB0047Y | | A012 | BJ | | D41472J | | 23 | | 115-199 |
| 0044 | 20 | | GK | | 4-0 | 33-24-11 | D05166 | | B3 | | | D41472J | | 21 | | 001-099 |
| 0044 | 20 | | GK | | 2-0 | 33-24-11 | D05166 | | 4 | | | D41472J | | 21 | | 115-199 |
| 0045 | 22 | | GK | | 4-0 | 33-24-11 | D02712 | | A1 | | | D41472J | | 24 | | 001-099 |
| 0045 | 22 | | GK | | 2-0 | 33-24-11 | D02712 | | A1 | | | D41472J | | 24 | | 115-199 |
| 0046 | 24 | | GK | | 5-0 | 33-24-11 | D41470J | | 2 | | | TB0047Z | | 15 | BJ | 001-099 |
| 0046 | 22 | | GK | | 3-0 | 33-24-11 | D41470J | | 2 | | | TB0047Z | | 15 | BJ | 115-199 |
| 0047 | 24 | | GK | | 2-0 | 33-24-11 | D41848J | | 4 | | | D41470J | | 1 | | 001-099 |
| 0047 | 22 | | GK | | 3-0 | 33-24-11 | D41848J | | 4 | | | TB0047Y | | C012 | BJ | 115-199 |
| 0048 | 24 | | GK | | 3-0 | 33-24-11 | D41848J | | 6 | | | D02712 | | X2 | | 001-099 |
| 0048 | 22 | | GK | | 2-0 | 33-24-11 | D41848J | | 6 | | | D02712 | | X2 | | 115-199 |
| 0049 | 24 | | GK | | 2-0 | 33-24-11 | TB0047Y | | C028 | BJ | | D02712 | | X1 | | 001-099 |
| 0049 | 22 | | GK | | 3-0 | 33-24-11 | D02712 | | X1 | | | TB0047Y | | C028 | BJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1240

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1240 | 286N1240 | | | INTERNAL P34 - PLATE COMPONENTS (continued) | | | | | | | | | | | |
| 0050 | 22 | | GK | | 2-0 | 33-24-11 | TB0047Y | A013 | BJ | | D02712 | A2 | | | ALL |
| 0051 | 22 | | GK | | 2-0 | 33-24-11 | TB0047Y | C013 | BJ | | D02712 | B2 | | | ALL |
| 0053 | 22 | | GK | | 2-0 | 33-24-11 | TB0047X | C006 | BJ | | D02714 | X2 | | | 115-199 |
| 0054 | 22 | | GK | | 2-0 | 33-24-11 | TB0047Y | C013 | BJ | | D02714 | X1 | | | 115-199 |
| 0055 | 22 | | GK | | 2-0 | 33-24-11 | TB0047Z | | 15 | BJ | D02714 | A2 | | | 115-199 |
| 0056 | 22 | | GK | | 3-0 | 33-24-11 | GD01170 | DC.. | 2 | | D02714 | A1 | | | 115-199 |
| 0057 | 24 | | GK | | 4-0 | 33-24-11 | TB0047Z | | 15 | BJ | D41848J | 5 | | | 001-099 |
| 0057 | 22 | | GK | | 3-0 | 33-24-11 | TB0047Z | | 15 | BJ | D41848J | 5 | | | 115-199 |
| 0058 | 24 | | GK | | 4-0 | 33-24-11 | D05166 | | X2 | | D41472J | 22 | | | 001-099 |
| 0058 | 22 | | GK | | 2-0 | 33-24-11 | D05166 | | 3 | | D41472J | 22 | | | 115-199 |
| 0060 | 22 | | GK | | 3-0 | 33-24-11 | D41470J | | 1 | | TB0047Y | C012 | BJ | | 115-199 |
| 0062 | 22 | | GK | | 2-0 | 33-26-31 | D03082 | | C3 | | TB0047Y | C029 | BJ | | 001-099 |
| 0062 | 22 | | GK | | 3-0 | 33-26-31 | D03082 | | C3 | | TB0047Y | C029 | BJ | | 115-199 |
| 0064 | 22 | | GK | | 2-0 | 33-27-11 | D03082 | | B1 | | TB0047X | D005 | BJ | | 001-099 |
| 0064 | 22 | | GK | | 2-0 | 33-27-11 | D03082 | | B1 | | TB0047Y | A011 | BJ | | 115-199 |
| 0069 | 22 | | GK | | 3-0 | 33-27-31 | D41472J | | 30 | | TB0047Z | 8 | BJ | | 115-199 |
| 0070 | 22 | | GK | | 3-0 | 33-27-31 | D41472J | | 31 | | TB0047Z | 10 | BJ | | 115-199 |
| 0072 | 24 | | GK | | 3-0 | 33-24-11 | K10028 | | X1 | C | TB0047Y | C028 | BJ | | 001-099 |
| 0072 | 22 | | GK | | 3-0 | 33-24-11 | K10028 | | X1 | C | TB0047Y | C028 | BJ | | 115-199 |
| 0073 | 24 | | GK | | 3-0 | 33-24-11 | D05166 | | X1 | | TB0047Y | C028 | BJ | | 001-099 |
| 0073 | 22 | | GK | | 3-0 | 33-24-11 | D05166 | | 7 | | TB0047Y | C028 | BJ | | 115-199 |
| 0074 | 24 | | GK | | 3-0 | 33-24-11 | D05166 | | A2 | | TB0047Z | 15 | BJ | | 001-099 |
| 0074 | 22 | | GK | | 3-0 | 33-24-11 | D05166 | | 6 | | TB0047Z | 15 | BJ | | 115-199 |
| 0075 | 20 | | GK | | 2-0 | 33-24-11 | D05166 | | B2 | | K10028 | A1 | D | * | 001-099 |
| 0075 | 20 | | GK | | 3-0 | 33-24-11 | D05166 | | 2 | | TB0047Y | A012 | BJ | | 115-199 |
| 0076 | 24 | | GK | | 3-0 | 33-24-11 | D05166 | | A1 | | GD01170 | DC.. | 2 | | 001-099 |
| 0076 | 22 | | GK | | 3-0 | 33-24-11 | D05166 | | 1 | | GD01170 | DC.. | 2 | | 115-199 |
| 0077 | 22 | | GK | | 2-0 | 33-22-11 | D03082 | | C2 | | TB0047Z | 7 | BJ | | 001-099 |
| 0077 | 22 | | GK | | 3-0 | 33-22-11 | D03082 | | C2 | | TB0047Z | 7 | BJ | | 115-199 |
| 0078 | 22 | | GK | | 5-0 | 33-26-31 | TB0047Y | C029 | BJ | | D41472J | 32 | | | 001-099 |
| 0078 | 22 | | GK | | 4-0 | 33-26-31 | TB0047Y | C029 | BJ | | D41472J | 32 | | | 115-199 |
| 0079 | 22 | | GK | | 3-0 | 33-14-41 | D03080 | | C3 | | D41470J | 19 | | | 001-099 |
| 0079 | 22 | | GK | | 2-0 | 33-14-41 | D03080 | | C3 | | D41470J | 19 | | | 115-199 |
| 0080 | 22 | | GK | | 3-0 | 33-14-41 | D03080 | | C2 | | TB0047Z | 7 | BJ | | ALL |
| 0086 | 22 | | GK | | 4-0 | 38-14-11 | D00050 | | A3 | | D41472J | 7 | | | 001-099 |
| 0086 | 22 | | GK | | 3-0 | 38-14-11 | D00050 | | A3 | | D41472J | 7 | | | 115-199 |
| 0087 | 22 | | GK | | 3-0 | 38-14-11 | D00050 | | A1 | | TB0047Z | 16 | BJ | | 001-099 |
| 0087 | 22 | | GK | | 2-0 | 38-14-11 | D00050 | | A1 | | TB0047Y | C017 | BJ | | 115-199 |
| 0088 | 22 | | GK | | 3-0 | 38-14-11 | D00050 | | X1 | | TB0047Z | 16 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1240

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1240 | 286N1240 | | | INTERNAL P34 - PLATE COMPONENTS (continued) | | | | | | | | | | | |
| 0088 | 22 | | GK | | 2-0 | 38-14-11 | D00050 | X1 | | | TB0047Y | C017 | BJ | | 115-199 |
| 0089 | 22 | | GK | | 3-0 | 38-14-11 | D00050 | X2 | | | GD01170 | DC.. | 2 | | ALL |
| 0090 | 22 | | GK | | 4-0 | 38-14-11 | D00050 | A2 | | | D41472J | 8 | | | 001-099 |
| 0090 | 22 | | GK | | 3-0 | 38-14-11 | D00050 | A2 | | | D41472J | 8 | | | 115-199 |
| 0100 | 20 | | GK | | 3-0 | 23-31-13 | D02712 | C1 | | | D41848J | 7 | | | 001-099 |
| 0100 | 20 | | GK | | 2-0 | 23-31-13 | D02712 | C1 | | | D41848J | 7 | | | 115-199 |
| 0101 | 20 | | GK | | 2-0 | 23-31-13 | D02712 | C2 | | | TB0047Y | A018 | BJ | | ALL |
| 0102 | 20 | | GK | | 3-0 | 23-31-13 | K10028 | C2 | D | | TB0047Y | A018 | BJ | | 001-099 |
| 0102 | 20 | | GK | | 2-0 | 23-31-13 | K10028 | C2 | D | | TB0047Y | A018 | BJ | | 115-199 |
| 0103 | 20 | | GK | | 4-0 | 23-31-13 | K10028 | C1 | D | | D41848J | 8 | | | 001-099 |
| 0103 | 20 | | GK | | 3-0 | 23-31-13 | K10028 | C1 | D | | D41848J | 8 | | | 115-199 |
| 0104 | 20 | | GK | | 4-0 | 23-31-11 | D41470J | 7 | | | TB0047Y | A018 | BJ | | 001-099 |
| 0104 | 20 | | GK | | 3-0 | 23-31-11 | D41470J | 7 | | | TB0047Y | A018 | BJ | | 115-199 |
| 0111 | 22 | | GK | | 3-0 | 33-51-11 | D41472J | 20 | | | D41474J | 16 | | | ALL |
| 0113 | 24 | | GK | | 4-0 | 33-24-11 | D41848J | 3 | | | K10028 | X2 | C | | 001-099 |
| 0113 | 22 | | GK | | 3-0 | 33-24-11 | D41848J | 3 | | | K10028 | X2 | C | | 115-199 |
| 0118 | 24 | | GK | | 4-0 | 24-51-51 | D41474J | 19 | | | TB0047X | A005 | BJ | | ALL |
| 0119 | 24 | | GK | | 4-0 | 24-51-51 | D41474J | 20 | | | TB0047X | B005 | BJ | | ALL |
| 0120 | 20 | | GK | | 4-0 | 24-51-51 | D41474J | 18 | | | TB0047X | D006 | BJ | | 001-099 |
| 0120 | 24 | | GK | | 4-0 | 24-51-51 | D41474J | 18 | | | TB0047X | D006 | BJ | | 115-199 |
| 0121 | 16 | | GK | | 5-0 | 28-21-11 | D41476J | 19 | | | TB0047F | A019 | 2 | | 001-099 |
| 0121 | 16 | | GK | | 3-0 | 28-21-11 | D41472J | 38 | 16 | | TB0047F | A019 | 2 | | 115-199 |
| 0122 | 16 | | GK | | 5-0 | 28-21-11 | D41476J | 17 | | | TB0047F | C019 | 2 | | 001-099 |
| 0122 | 16 | | GK | | 3-0 | 28-21-11 | D41472J | 36 | 16 | | TB0047F | C019 | 2 | | 115-199 |
| 0123 | 16 | | GK | | 5-0 | 28-21-11 | D41476J | 18 | | | TB0047F | A024 | 2 | | 001-099 |
| 0123 | 16 | | GK | | 3-0 | 28-21-11 | D41472J | 37 | 16 | | TB0047F | A024 | 2 | | 115-199 |
| 0125 | 24 | | GK | | 3-0 | 33-21-11 | D41472J | 11 | | | D41474J | 14 | | | ALL |
| 0126 | 22 | | GK | | 3-0 | 33-51-11 | D41470J | 18 | | | D41474J | 15 | | | ALL |
| 0127 | 22 | | GK | | 3-0 | 33-51-11 | D41470J | 20 | | | D41474J | 17 | | | ALL |
| 0128 | 24 | | GK | | 3-0 | 33-21-31 | D41472J | 45 | | | D41474J | 10 | | | ALL |
| 0131 | 24 | | GK | | 5-0 | 24-41-12 | D41470J | 8 | | | TB0047X | C005 | BJ | | 001-099 |
| 0131 | 24 | | GK | | 3-0 | 24-41-12 | D41470J | 8 | | | TB0047X | C021 | BJ | | 115-199 |
| 0132 | 22 | | GK | | 4-0 | 33-22-11 | TB0047Z | 8 | BJ | | D41474J | 6 | | | 115-199 |
| 0136 | 22 | | GK | | 3-0 | 33-22-11 | D41474J | 8 | | | D03082 | A1 | | | ALL |
| 0137 | 24 | | GK | | 3-0 | 33-22-11 | D03082 | X2 | | | D41474J | 22 | | | ALL |
| 0138 | 22 | | GK | | 4-0 | 33-22-11 | D41470J | 38 | | | TB0047Y | A028 | BJ | | ALL |
| 0139 | 22 | | GK | | 2-0 | 33-22-11 | D03082 | A2 | | | TB0047Y | A014 | BJ | | ALL |
| 0155 | 24 | | GK | | 5-0 | 24-51-71 | D41470J | 9 | | | TB0047X | B006 | BJ | | 001-099 |
| 0155 | 24 | | GK | | 3-0 | 24-51-71 | D41470J | 9 | | | TB0047X | B023 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1240

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1240 | 286N1240 | | | | INTERNAL P34 - PLATE COMPONENTS (continued) | | | | | | | | | | | | |
| 0159 | 22 | | GK | | 3-0 | 33-22-11 | D07210 | | B1 | | | TB0047Z | 33 | BJ | | 001-099 | |
| 0159 | 22 | | GA | | 2-0 | 33-22-11 | D07210 | | B1 | | | TB0047Z | 33 | BJ | | 115-199 | |
| 0161 | 16 | | GK | | 3-0 | 33-21-11 | GD00461 | | AC.. | E | | T10003 | GND | E | | 001-099 | |
| 0163 | 16 | | GK | | 3-0 | 33-21-11 | GD00461 | | AC.. | E | | T10004 | GND | E | | 001-099 | |
| 0164 | 20 | | GK | | 2-0 | 33-21-11 | D40476J | | 1 | | | T10003 | HV2 | E | | 001-099 | |
| 0165 | 20 | | GK | | 3-0 | 33-21-11 | D40376J | | 1 | | | T10004 | HV2 | E | | 001-099 | |
| 0184 | 22 | | GK | | 3-0 | 33-22-11 | D07210 | | A1 | | | TB0047Z | 33 | BJ | | 001-099 | |
| 0184 | 22 | | GA | | 2-0 | 33-22-11 | D07210 | | A1 | | | TB0047Z | 33 | BJ | | 115-199 | |
| 0185 | 24 | | GK | | 4-0 | 33-21-11 | TB0047Y | | C003 | BJ | | D40476J | 3 | | | 001-099 | |
| 0188 | 24 | | GK | | 4-0 | 33-21-11 | TB0047Y | | C003 | BJ | | D40376J | 3 | | | 001-099 | |
| 0189 | 24 | | GK | | 4-0 | 33-21-11 | TB0047Y | | C003 | BJ | | D41474J | 12 | | | 001-099 | |
| 0220 | 24 | | GK | | 4-0 | 33-21-31 | TB0047Y | | A011 | BJ | | D40474J | 3 | | | 001-099 | |
| 0220 | 24 | | GK | | 4-0 | 33-21-31 | D40474J | | 3 | | | TB0047Y | A004 | BJ | | 115-199 | |
| 0221 | 24 | | GK | | 4-0 | 33-21-31 | TB0047Y | | A011 | BJ | | D40374J | 3 | | | 001-099 | |
| 0221 | 24 | | GK | | 4-0 | 33-21-31 | D40374J | | 3 | | | TB0047Y | A004 | BJ | | 115-199 | |
| 0222 | 24 | | GK | | 4-0 | 33-21-31 | TB0047Y | | A011 | BJ | | D41474J | 9 | | | 001-099 | |
| 0222 | 24 | | GK | | 4-0 | 33-21-31 | D41474J | | 9 | | | TB0047Y | A004 | BJ | | 115-199 | |
| 0225 | 22 | | GK | | 2-0 | 33-22-11 | TB0047Z | | 8 | BJ | | D04838 | X1 | | | 115-199 | |
| 0226 | 20 | | GK | | 2-0 | 33-22-11 | D41472J | | 9 | | | D04838 | A2 | | | 115-199 | |
| 0227 | 20 | | GK | | 2-0 | 33-22-11 | D04838 | | A1 | | | TB0047X | A006 | BJ | | 115-199 | |
| 0228 | 22 | | GK | | 3-0 | 33-22-11 | D04838 | | X2 | | | GD01170 | AC.. | 2 | | 115-199 | |
| 0232 | 22 | | GK | | 3-0 | 33-21-51 | D41474J | | 4 | | | D41472J | 48 | | | 001-099 | |
| 0233 | 22 | | GK | | 4-0 | 33-22-11 | D07210 | | A3 | | | D41474J | 30 | | | 001-099 | |
| 0233 | 22 | | GA | | 3-0 | 33-22-11 | D07210 | | A3 | | | D41474J | 30 | | | 115-199 | |
| 0238 | 22 | | GK | | 4-0 | 33-21-51 | D40476J | | 10 | | | TB0047Y | A029 | BJ | | 001-099 | |
| 0239 | 22 | | GK | | 4-0 | 33-21-51 | D40376J | | 10 | | | TB0047Y | A029 | BJ | | 001-099 | |
| 0265 | 22 | | GK | | 5-0 | 33-21-51 | D41472J | | 28 | | | TB0047Y | A029 | BJ | | 001-099 | |
| 0265 | 22 | | GA | | 3-0 | 33-21-51 | TB0047Y | | C004 | BJ | | D41472J | 28 | | | 115-199 | |
| 0266 | 22 | | GK | | 5-0 | 33-21-51 | D41472J | | 29 | | | TB0047Y | A030 | BJ | | 001-099 | |
| 0266 | 22 | | GA | | 4-0 | 33-21-51 | TB0047Y | | A030 | BJ | | D41472J | 29 | | | 115-199 | |
| 0274 | 22 | | GK | | 4-0 | 33-22-11 | D07210 | | A2 | | | D41474J | 31 | | | 001-099 | |
| 0274 | 22 | | GA | | 3-0 | 33-22-11 | D07210 | | A2 | | | D41474J | 31 | | | 115-199 | |
| 0275 | 22 | | GK | | 4-0 | 33-22-11 | D07210 | | X2 | | | D41472J | 18 | | | 001-099 | |
| 0275 | 22 | | GA | | 2-0 | 33-22-11 | D07210 | | X2 | | | D41472J | 26 | | | 115-199 | |
| 0276 | 22 | | GK | | 3-0 | 33-22-11 | D07210 | | X1 | | | TB0047Z | 33 | BJ | | 001-099 | |
| 0276 | 22 | | GA | | 2-0 | 33-22-11 | D07210 | | X1 | | | TB0047Z | 33 | BJ | | 115-199 | |
| 0277 | 22 | | GA | | 3-0 | 33-22-12 | D07210 | | C3 | | | D41474J | 28 | | | 115-199 | |
| 0278 | 22 | | GA | | 3-0 | 33-22-12 | D07210 | | C2 | | | D41474J | 29 | | | 115-199 | |
| 0279 | 22 | | GA | | 2-0 | 33-22-11 | D07210 | | C1 | | | TB0047Z | 33 | BJ | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1240

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | | To | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1240 | 286N1240 | | | INTERNAL P34 - PLATE COMPONENTS (continued) | | | | | | | | | | | | |
| 0281 | 22 | | GK | | 4-0 | 33-22-14 | D07210 | B2 | | | D41474J | 23 | | | 001-099 | |
| 0281 | 22 | | GA | | 3-0 | 33-22-14 | D07210 | B2 | | | D41474J | 26 | | | 115-199 | |
| 0282 | 22 | | GK | | 4-0 | 33-22-14 | D07210 | B3 | | | D41474J | 28 | | | 001-099 | |
| 0282 | 22 | | GA | | 3-0 | 33-22-14 | D07210 | B3 | | | D41474J | 27 | | | 115-199 | |
| 0382 | 24 | | GK | | 4-0 | 31-31-62 | D41470J | 39 | | | K10028 | X2 | C | | 001-099 | |
| 0422 | 22 | | GK | | 4-0 | 33-22-11 | D41474J | 3 | | | T10022 | HV2 | E | | 001-099 | |
| 0423 | 22 | | GK | | 4-0 | 33-22-11 | T10022 | LV | E | | D41474J | 6 | | | 001-099 | |
| 0424 | 20 | | GK | | 3-0 | 33-22-11 | T10022 | GND | E | | GD00461 | AC.. | E | | 001-099 | |
| 0425 | 24 | | GK | | 5-0 | 33-24-11 | D03262 | 2 | | | TB0047Z | 15 | BJ | | 001-099 | |
| 0426 | 24 | | GK | | 5-0 | 33-24-11 | D03262 | 1 | | | GD01170 | DC.. | 2 | | 001-099 | |
| 0427 | 24 | | GK | | 5-0 | 33-42-12 | D41472J | 33 | | | TB0047Y | C014 | BJ | | 001-099 | |
| 0428 | 20 | | GK | | 3-0 | 33-42-12 | D41848J | 1 | | | D05092 | A2 | | | 001-099 | |
| 0430 | 24 | | GK | | 4-0 | 33-42-12 | D41470J | 3 | | | TB0047A | C026 | 2 | | 001-099 | |
| 0431 | 24 | | GK | | 4-0 | 33-42-12 | D41470J | 4 | | | TB0047Y | C014 | BJ | | 001-099 | |
| 0432 | 24 | | GK | | 4-0 | 33-42-12 | D41470J | 5 | | | TB0047A | A026 | 2 | | 001-099 | |
| 0433 | 24 | | GK | | 4-0 | 33-42-12 | D41470J | 6 | | | D05094 | X2 | | | 001-099 | |
| 0435 | 24 | | GK | | 2-0 | 33-42-12 | TB0047Y | C014 | BJ | | D05094 | X1 | | | 001-099 | |
| 0436 | 24 | | GK | | 2-0 | 33-42-12 | TB0047Y | C014 | BJ | | D05092 | X1 | | | 001-099 | |
| 0437 | 24 | | GK | | 2-0 | 33-42-12 | TB0047A | A026 | 2 | | D05092 | X2 | | | 001-099 | |
| 0438 | 20 | | GK | | 4-0 | 33-42-12 | D41472J | 35 | | | D05092 | A1 | | | 001-099 | |
| 0439 | 20 | | GK | | 4-0 | 33-42-12 | D41472J | 34 | | | D05092 | A3 | | | 001-099 | |
| 0440 | 20 | | GK | | 4-0 | 33-42-21 | D41472J | 39 | | | D05094 | B1 | | | 001-099 | |
| 0441 | 20 | | GK | | 3-0 | 33-42-21 | D41848J | 14 | | | D05094 | B2 | | | 001-099 | |
| W1242 | 286N1242 | | | INTERNAL P34 - LARGE COMPONENTS | | | | | | | | | | | | |
| 0001 | 16 | | GK | | 4-5 | 33-21-11 | T10003 | LV | E | | TB0047F | A002 | 2 | | 115-199 | |
| 0002 | 20 | | GK | | 3-2 | 33-21-11 | T10003 | HV2 | E | | D40476J | 1 | | | 115-199 | |
| 0003 | 16 | | GK | | 2-4 | 33-21-11 | T10003 | GND | E | | GD00461 | AC.. | E | | 115-199 | |
| 0004 | 16 | | GK | | 4-9 | 33-21-11 | T10004 | LV | E | | TB0047F | C002 | 2 | | 115-199 | |
| 0005 | 20 | | GK | | 3-3 | 33-21-11 | T10004 | HV2 | E | | D40376J | 1 | | | 115-199 | |
| 0006 | 16 | | GK | | 2-8 | 33-21-11 | T10004 | GND | E | | GD00461 | AC.. | E | | 115-199 | |
| 0007 | 24 | | GK | | 4-0 | 33-21-11 | D40476J | 3 | | | TB0047Y | A003 | BJ | | 115-199 | |
| 0008 | 24 | | GK | | 3-10 | 33-21-11 | D40376J | 3 | | | TB0047Y | A003 | BJ | | 115-199 | |
| 0009 | 24 | | GK | | 4-11 | 33-21-11 | TB0047Y | A003 | BJ | | D41474J | 12 | | | 115-199 | |
| 0019 | 22 | | GK | | 4-0 | 33-21-51 | D40476J | 4 | | | TB0047Y | C004 | BJ | | 115-199 | |
| 0020 | 22 | | GK | | 3-10 | 33-21-51 | D40376J | 4 | | | TB0047Y | C004 | BJ | | 115-199 | |
| 0021 | 22 | | GA | | 3-10 | 33-21-51 | D41474J | 4 | | | D41472J | 48 | | | 115-199 | |
| 0022 | 22 | | GK | | 3-11 | 33-22-11 | T10022 | HV2 | E | | TB0047Z | 10 | BJ | | 115-199 | |
| 0023 | 20 | | GK | | 4-0 | 33-22-11 | T10022 | LV | E | | TB0047X | A006 | BJ | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1240

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|----|-------------|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1242 | 286N1242 | | | | INTERNAL P34 - LARGE COMPONENTS (continued) | | | | | | | | | | | |
| 0024 | 20 | | GK | | 2-0 | 33-22-11 | T10022 | GND | E | | GD00460 | AC.. | E | | 115-199 | |
| 0025 | 22 | | GK | | 4-6 | 33-24-11 | D03262 | 2 | | | TB0047X | C006 | BJ | | 115-199 | |
| 0026 | 22 | | GK | | 2-6 | 33-24-11 | D03262 | 1 | | | GD00460 | AC.. | E | | 115-199 | |
| 0027 | 20 | | GK | | 3-11 | 33-42-12 | D41472J | 33 | | | TB0047Y | C014 | BJ | | 115-199 | |
| 0028 | 20 | | GK | | 3-4 | 33-42-12 | D41848J | 1 | | | K00162 | A2 | E | | 115-199 | |
| 0029 | 20 | | GK | | 3-7 | 33-42-12 | D41848J | 2 | | | K00435 | A2 | E | | 115-199 | |
| 0030 | 20 | | GK | | 3-9 | 33-42-12 | D41470J | 3 | | | TB0047A | C041 | 2 | | 115-199 | |
| 0031 | 20 | | GK | | 3-10 | 33-42-12 | D41470J | 4 | | | TB0047Y | C014 | BJ | | 115-199 | |
| 0032 | 20 | | GK | | 3-9 | 33-42-12 | D41470J | 5 | | | TB0047A | A041 | 2 | | 115-199 | |
| 0033 | 20 | | GK | | 3-8 | 33-42-12 | D41470J | 6 | | | K00435 | X2 | C | | 115-199 | |
| 0034 | 20 | | GK | | 3-10 | 33-42-12 | D41472J | 44 | | | K00435 | A1 | E | | 115-199 | |
| 0035 | 20 | | GK | | 4-8 | 33-42-12 | K00435 | X1 | C | | TB0047Y | C014 | BJ | | 115-199 | |
| 0036 | 20 | | GK | | 4-5 | 33-42-12 | K00162 | X1 | C | | TB0047Y | C014 | BJ | | 115-199 | |
| 0037 | 20 | | GK | | 4-4 | 33-42-12 | K00162 | X2 | C | | TB0047A | A041 | 2 | | 115-199 | |
| 0038 | 20 | | GK | | 3-6 | 33-42-12 | D41472J | 35 | | | K00162 | A1 | E | | 115-199 | |
| 0039 | 20 | | GK | | 3-6 | 33-42-12 | D41472J | 34 | | | K00162 | A3 | E | | 115-199 | |
| 0040 | 20 | | GK | | 3-10 | 33-42-21 | D41472J | 39 | | | K00435 | B1 | E | | 115-199 | |
| 0041 | 20 | | GK | | 3-7 | 33-42-21 | D41848J | 14 | | | K00435 | B2 | E | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1240

Page 7 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | To | | | | Effectivity | | | | | | |
|------------|-------------|----|-------|-------------------------|------|----------|---------|---------|-------|-------------|------|---------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Diagram | Equip | | Term | Type | Splice | Equip | Term | Type |
| W1250 | 286N1250 | | | INTERNAL P70- PLATE 'E' | | | | | | | | | | | | |
| 0001 | 14 | | HA | | 3-2 | 21-25-11 | D41934J | 14 | | | | K00415 | A2 | E | | 001-099 |
| 0001 | 14 | | HA | | 5-0 | 21-25-11 | D41934J | 14 | | | | K00415 | A2 | E | | 115-199 |
| 0002 | 14 | | HA | | 3-2 | 21-25-11 | D41934J | 16 | | | | K00415 | B2 | E | | 001-099 |
| 0002 | 14 | | HA | | 5-0 | 21-25-11 | D41934J | 16 | | | | K00415 | B2 | E | | 115-199 |
| 0003 | 14 | | HA | | 3-2 | 21-25-11 | D41934J | 18 | | | | K00415 | C2 | E | * | 001-099 |
| 0003 | 14 | | HA | | 5-0 | 21-25-11 | D41934J | 18 | | | | K00415 | C2 | E | * | 115-199 |
| 0004 | 24 | | GK | | 4-3 | 21-25-11 | D42074J | 10 | | | | K00415 | X1 | C | | 001-099 |
| 0004 | 24 | | GK | | 2-0 | 21-25-11 | D42074J | 10 | | | | K00415 | X1 | C | | 115-199 |
| 0005 | 24 | | GK | | 3-8 | 21-25-11 | D41746J | 11 | | | | K00415 | X2 | C | | 001-099 |
| 0005 | 24 | | GK | | 4-0 | 21-25-11 | D41746J | 11 | | | | K00415 | X2 | C | | 115-199 |
| 0009 | 20 | | GK | | 2-3 | 21-43-11 | K10057 | A1 | D | | | D41934J | 11 | | | 001-099 |
| 0009 | 20 | | GK | | 4-0 | 21-43-11 | K10057 | A1 | D | | | D41934J | 11 | | | 115-199 |
| 0010 | 20 | | GK | | 2-3 | 21-43-11 | K10057 | B1 | D | | | D41934J | 12 | | | 001-099 |
| 0010 | 20 | | GK | | 4-0 | 21-43-11 | K10057 | B1 | D | | | D41934J | 12 | | | 115-199 |
| 0011 | 20 | | GK | | 2-7 | 21-43-11 | K10057 | C1 | D | | | TB0155Y | C007 | BJ | | 001-099 |
| 0011 | 20 | | GK | | 5-0 | 21-43-11 | K10057 | C1 | D | | | TB0155X | A001 | BJ | | 115-199 |
| 0012 | 24 | | GK | | 2-3 | 21-43-11 | K10057 | X1 | C | | | D41934J | 9 | | | 001-099 |
| 0012 | 24 | | GK | | 4-0 | 21-43-11 | K10057 | X1 | C | | | D41934J | 9 | | | 115-199 |
| 0013 | 24 | | GK | | 2-6 | 21-43-11 | K10057 | X2 | C | | | TB0155Y | C003 | BJ | | 001-099 |
| 0013 | 24 | | GK | | 3-0 | 21-43-11 | K10057 | X2 | C | | | TB0155Y | C003 | BJ | | 115-199 |
| 0014 | 24 | | GK | | 3-8 | 21-43-11 | D41934J | 8 | | | | TB0155Y | C003 | BJ | | 001-099 |
| 0014 | 24 | | GK | | 5-0 | 21-43-11 | D41934J | 8 | | | | TB0155Y | C003 | BJ | | 115-199 |
| 0015 | 24 | | GK | | 1-11 | 21-43-11 | D42074J | 6 | | | | D41934J | 10 | | | 001-099 |
| 0015 | 24 | | GK | | 6-0 | 21-43-11 | D42074J | 6 | | | | TB0155Y | A003 | BJ | | 115-199 |
| 0016 | 24 | | GK | | 5-0 | 21-43-11 | D41934J | 10 | | | | TB0155Y | A003 | BJ | | 115-199 |
| 0017 | 14 | | HA | | 3-7 | 21-44-11 | D41942J | 14 | | | | K10083 | A2 | E | | 001-099 |
| 0017 | 14 | | HA | | 6-0 | 21-44-11 | D41942J | 14 | | | | K10083 | A2 | E | | 115-199 |
| 0018 | 14 | | HA | | 3-7 | 21-44-11 | D41942J | 16 | | | | K10083 | B2 | E | | 001-099 |
| 0018 | 14 | | HA | | 6-0 | 21-44-11 | D41942J | 16 | | | | K10083 | B2 | E | | 115-199 |
| 0019 | 14 | | HA | | 3-7 | 21-44-11 | D41942J | 18 | | | | K10083 | C2 | E | | 001-099 |
| 0019 | 14 | | HA | | 6-0 | 21-44-11 | D41942J | 18 | | | | K10083 | C2 | E | | 115-199 |
| 0020 | 22 | | GK | | 5-0 | 21-44-11 | D41880J | 14 | | | | K10083 | X1 | C | * | 001-099 |
| 0020 | 22 | | GK | | 3-0 | 21-44-11 | D41880J | 14 | | | | K10083 | X1 | C | * | 115-199 |
| 0021 | 22 | | GK | | 3-7 | 21-44-11 | D41942J | 1 | | | | K10083 | X1 | C | * | 001-099 |
| 0021 | 22 | | GK | | 3-0 | 21-44-11 | D41942J | 1 | | | | K10083 | X1 | C | * | 115-199 |
| 0022 | 22 | | GK | | 3-7 | 21-44-11 | D41942J | 2 | | | | K10083 | X2 | C | | 001-099 |
| 0022 | 22 | | GK | | 3-0 | 21-44-11 | D41942J | 2 | | | | K10083 | X2 | C | | 115-199 |
| 0023 | 22 | | GK | | 1-6 | 21-44-11 | D41942J | 3 | | | | D42074J | 9 | | | 001-099 |
| 0023 | 22 | | GK | | 2-0 | 21-44-11 | D41942J | 3 | | | | D42074J | 9 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1250 | 286N1250 | | | INTERNAL P70- PLATE 'E' (continued) | | | | | | | | | | | |
| 0024 | 20 | | GK | | 2-10 | 24-51-14 | K00119 | 13 | C | | GD01661 | DC.. | F | | 001-099 |
| 0024 | 20 | | GK | | 3-0 | 24-51-14 | K00119 | 13 | C | | GD01661 | DC.. | F | | 115-199 |
| 0025 | 20 | | GK | | 2-11 | 24-51-14 | K00119 | X1 | C | * | D41968J | 9 | | | 001-099 |
| 0025 | 20 | | GK | | 4-0 | 24-51-14 | K00119 | X1 | C | * | D41968J | 9 | | | 115-199 |
| 0026 | 20 | | GK | | 1-8 | 24-51-14 | K00119 | X2 | C | | D42074J | 1 | | | 001-099 |
| 0026 | 20 | | GK | | 3-0 | 24-51-14 | K00119 | X2 | C | * | D42074J | 1 | | | 115-199 |
| 0027 | 20 | | GK | | 3-8 | 24-51-14 | K00119 | 14 | C | | D42074J | 2 | | | 001-099 |
| 0027 | 20 | | GK | | 2-0 | 24-51-14 | K10297 | 14 | C | | D42074J | 2 | | | 115-199 |
| 0028 | 20 | | GK | | 1-9 | 24-53-11 | T00123 | HV | E | | D41746J | 3 | | | 001-099 |
| 0028 | 20 | | GK | | 3-0 | 24-53-11 | T00123 | HV | E | | D41746J | 3 | | | 115-199 |
| 0029 | 14 | | HA | | 4-0 | 24-53-11 | T00123 | GND | E | | GD01662 | AC.. | F | | ALL |
| 0030 | 14 | | HA | | 1-8 | 24-53-11 | T00123 | LV | E | | D41746J | 14 | | | 001-099 |
| 0030 | 14 | | HA | | 3-0 | 24-53-11 | T00123 | LV | E | | D41746J | 14 | | | 115-199 |
| 0031 | 24 | | GK | | 3-1 | 27-51-61 | D04094 | 3 | | | D41968J | 14 | | | 001-099 |
| 0031 | 22 | | GK | | 4-0 | 27-51-61 | D04094 | 3 | | | D41968J | 14 | | | 115-199 |
| 0032 | 24 | | GK | | 3-1 | 27-51-61 | D04094 | 5 | | | D41968J | 16 | | | 001-099 |
| 0032 | 22 | | GK | | 4-0 | 27-51-61 | D04094 | 5 | | | D41968J | 16 | | | 115-199 |
| 0033 | 20 | | GK | | 4-0 | 27-51-61 | D04094 | 1 | | | GD01660 | AC.. | 2 | | 001-099 |
| 0033 | 20 | | GK | | 5-0 | 27-51-61 | D04094 | 1 | | | GD01660 | AC.. | 2 | | 115-199 |
| 0034 | 20 | | GK | | 4-0 | 27-51-61 | D04094 | 6 | | | GD01660 | ST.. | 2 | | 001-099 |
| 0034 | 20 | | GK | | 5-0 | 27-51-61 | D04094 | 6 | | | GD01660 | ST.. | 2 | | 115-199 |
| 0035 | 08 | | HA | | 4-2 | 24-51-14 | K00119 | A1 | E | | TB5050 | 4 | E | | 001-099 |
| 0035 | 08 | | HA | | 1-9 | 24-51-14 | K00119 | A1 | E | | TB5050 | 10 | E | | 115-199 |
| 0036 | 08 | | HA | | 4-3 | 24-51-14 | K00119 | B1 | E | | TB5050 | 5 | E | | 001-099 |
| 0036 | 08 | | HA | | 1-9 | 24-51-14 | K00119 | B1 | E | | TB5050 | 11 | E | | 115-199 |
| 0037 | 08 | | HA | | 4-4 | 24-51-14 | K00119 | C1 | E | | TB5050 | 6 | E | | 001-099 |
| 0037 | 08 | | HA | | 1-9 | 24-51-14 | K00119 | C1 | E | | TB5050 | 12 | E | | 115-199 |
| 0038 | 20 | | GK | | 3-8 | 21-43-11 | D41934J | 13 | | | TB0155Y | C007 | BJ | | 001-099 |
| 0038 | 20 | | GK | | 5-0 | 21-43-11 | D41934J | 13 | | | TB0155X | A001 | BJ | | 115-199 |
| 0039 | 22 | | GK | | 4-5 | 21-25-11 | D42074J | 3 | | | TB0155X | A002 | BJ | | 001-099 |
| 0039 | 22 | | GK | | 5-0 | 21-25-11 | D42074J | 3 | | | TB0155X | A002 | BJ | | 115-199 |
| 0040 | 22 | | GK | | 4-5 | 21-25-11 | D42074J | 4 | | | TB0155Y | A008 | BJ | | 001-099 |
| 0040 | 22 | | GK | | 3-0 | 21-25-11 | D42074J | 4 | | | TB0155Y | A008 | BJ | | 115-199 |
| 0041 | 24 | | GK | | 4-3 | 21-51-11 | D42074J | 7 | | | K00415 | 11 | C | | 001-099 |
| 0041 | 24 | | GK | | 2-0 | 21-51-11 | D42074J | 7 | | | K00415 | 11 | C | | 115-199 |
| 0042 | 24 | | GK | | 4-0 | 21-43-11 | D42074J | 5 | | | D06912 | A3 | | | 001-099 |
| 0042 | 24 | | GK | | 5-0 | 21-43-11 | D42074J | 5 | | | TB0155X | D002 | BJ | | 115-199 |
| 0043 | 20 | | GK | | 4-0 | 33-45-11 | D04754 | A1 | | | D42074J | 20 | | | 001-099 |
| 0043 | 20 | | GK | | 5-0 | 33-45-11 | D04754 | A1 | | | D42074J | 20 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1250 | | | | | | | | | | | | | | | |
| | | 286N1250 | | | | INTERNAL P70- PLATE 'E' (continued) | | | | | | | | | |
| 0044 | 20 | GK | | | 4-0 | 33-45-11 | D04754 | B1 | | | D42074J | 19 | | | 001-099 |
| 0044 | 20 | GK | | | 5-0 | 33-45-11 | D04754 | B1 | | | D42074J | 19 | | | 115-199 |
| 0045 | 22 | GK | | | 4-0 | 33-45-11 | D04754 | X2 | | | D42074J | 18 | | | 001-099 |
| 0045 | 22 | GK | | | 5-0 | 33-45-11 | D04754 | X2 | | | D42074J | 18 | | | 115-199 |
| 0046 | 20 | GK | | | 2-0 | 33-45-11 | D04754 | X1 | | | TB0155Y | A004 | BJ | | 001-099 |
| 0046 | 20 | GK | | | 3-0 | 33-45-11 | D04754 | X1 | | | TB0155Y | A004 | BJ | | 115-199 |
| 0047 | 20 | GK | | | 2-0 | 33-45-11 | D04754 | B2 | | | TB0155Y | A004 | BJ | | 001-099 |
| 0047 | 20 | GK | | | 3-0 | 33-45-11 | D04754 | B2 | | | TB0155Y | A004 | BJ | | 115-199 |
| 0048 | 20 | GK | | | 2-0 | 33-45-11 | D04754 | A2 | | | TB0155X | B001 | BJ | | 001-099 |
| 0048 | 20 | GK | | | 3-0 | 33-45-11 | D04754 | A2 | | | TB0155X | B001 | BJ | | 115-199 |
| 0050 | 20 | GK | | | 3-0 | 24-51-14 | K10297 | X1 | C | | K00119 | X1 | C | * | 115-199 |
| 0052 | 20 | GK | | | 3-0 | 24-51-14 | K10297 | X2 | C | | K00119 | X2 | C | * | 115-199 |
| 0053 | 20 | GK | | | 3-0 | 24-51-14 | K10297 | 13 | C | | K00119 | 14 | C | | 115-199 |
| 0057 | 16 | GK | | | 4-9 | 28-25-11 | D41968J | 15 | | | K00191 | A1 | D | | 001-099 |
| 0057 | 16 | GK | | | 6-0 | 28-25-11 | D41968J | 15 | | | K00191 | A1 | D | | 115-199 |
| 0058 | 16 | GK | | | 3-8 | 28-25-11 | D40022J | 15 | | | K00191 | A2 | D | | 001-099 |
| 0058 | 16 | GK | | | 5-0 | 28-25-11 | D40022J | 15 | | | K00191 | A2 | D | | 115-199 |
| 0059 | 20 | GK | | | 3-8 | 28-25-11 | D40022J | 2 | | | K00191 | X2 | C | | 001-099 |
| 0059 | 20 | GK | | | 5-0 | 28-25-11 | D40022J | 2 | | | K00191 | X2 | C | | 115-199 |
| 0060 | 20 | GK | | | 5-3 | 28-25-11 | D41968J | 17 | | | D02408 | X1 | | | 001-099 |
| 0060 | 20 | GK | | | 6-0 | 28-25-11 | D42166J | 5 | | | D02408 | X1 | | | 115-199 |
| 0061 | 24 | GK | | | 5-3 | 28-25-11 | D41968J | 18 | | | D02408 | A2 | | | 001-099 |
| 0061 | 24 | GK | | | 6-0 | 28-25-11 | D41968J | 18 | | | D02408 | A2 | | | 115-199 |
| 0062 | 24 | GK | | | 1-11 | 28-25-11 | D02408 | A1 | | | TB0155Y | A005 | BJ | | 001-099 |
| 0062 | 24 | GK | | | 3-0 | 28-25-11 | D02408 | A1 | | | TB0155Y | A005 | BJ | | 115-199 |
| 0063 | 22 | GK | | | 5-2 | 28-25-11 | D41968J | 20 | | | D04684 | C3 | | | 001-099 |
| 0063 | 22 | GK | | | 6-0 | 28-25-11 | D41968J | 20 | | | D04684 | C3 | | | 115-199 |
| 0064 | 20 | GK | | | 1-7 | 28-25-11 | D02408 | X2 | | | GD01660 | AC.. | 2 | | 001-099 |
| 0064 | 20 | GK | | | 3-0 | 28-25-11 | D02408 | X2 | | | GD01660 | AC.. | 2 | | 115-199 |
| 0065 | 24 | GK | | | 4-7 | 28-25-11 | D40022J | 5 | | | TB0155Y | C005 | BJ | | 001-099 |
| 0065 | 24 | GK | | | 6-0 | 28-25-11 | D40022J | 5 | | | TB0155Y | C005 | BJ | | 115-199 |
| 0066 | 22 | GK | | | 1-9 | 28-25-11 | D04684 | C2 | | | K00191 | X1 | C | | 001-099 |
| 0066 | 22 | GK | | | 2-0 | 28-25-11 | D04684 | C2 | | | K00191 | X1 | C | | 115-199 |
| 0067 | 22 | GK | | | 1-11 | 28-25-11 | D04684 | A2 | | | TB0155Y | A006 | BJ | | 001-099 |
| 0067 | 22 | GK | | | 2-0 | 28-25-11 | D04684 | A2 | | | TB0155Y | A006 | BJ | | 115-199 |
| 0068 | 20 | GK | | | 4-1 | 28-25-11 | D04684 | A1 | | | D40022J | 1 | | | 001-099 |
| 0068 | 20 | GK | | | 5-0 | 28-25-11 | D04684 | A1 | | | D40022J | 1 | | | 115-199 |
| 0069 | 22 | GK | | | 1-11 | 28-25-11 | D04684 | X2 | | | TB0155Y | A006 | BJ | | 001-099 |
| 0069 | 22 | GK | | | 2-0 | 28-25-11 | D04684 | X2 | | | TB0155Y | A006 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1250 | 286N1250 | | | INTERNAL P70- PLATE 'E' (continued) | | | | | | | | | | | |
| 0070 | 24 | | GK | | 1-11 | 28-25-11 | D04684 | | X1 | | TB0155Y | A005 | BJ | | 001-099 |
| 0070 | 24 | | GK | | 2-0 | 28-25-11 | D04684 | | X1 | | TB0155Y | A005 | BJ | | 115-199 |
| 0071 | 22 | | GK | | 2-2 | 28-25-11 | D04686 | | 8 | | TB0155Y | A006 | BJ | | 001-099 |
| 0071 | 22 | | GK | | 2-0 | 28-25-11 | D04686 | | A3 | | TB0155Y | A006 | BJ | | 115-199 |
| 0072 | 24 | | GK | | 2-2 | 28-25-11 | D04686 | | 3 | | TB0155Y | C005 | BJ | | 001-099 |
| 0072 | 24 | | GK | | 2-0 | 28-25-11 | D04686 | | X2 | | TB0155Y | C005 | BJ | | 115-199 |
| 0073 | 24 | | GK | | 2-2 | 28-25-11 | D04686 | | 7 | | TB0155Y | A005 | BJ | | 001-099 |
| 0073 | 24 | | GK | | 2-0 | 28-25-11 | D04686 | | X1 | | TB0155Y | A005 | BJ | | 115-199 |
| 0074 | 24 | | GK | | 2-2 | 28-25-11 | D04686 | | 6 | | TB0155Y | C005 | BJ | | 001-099 |
| 0074 | 24 | | GK | | 2-0 | 28-25-11 | D04686 | | A2 | | TB0155Y | C005 | BJ | | 115-199 |
| 0075 | 20 | | GK | | 3-6 | 28-22-11 | D42166J | | 1 | | D04684 | B2 | | | 001-099 |
| 0075 | 20 | | GK | | 5-0 | 28-22-11 | D42166J | | 1 | | D04684 | B2 | | | 115-199 |
| 0076 | 20 | | GK | | 3-6 | 28-22-11 | D42166J | | 2 | | D04684 | B1 | | | 001-099 |
| 0076 | 20 | | GK | | 5-0 | 28-22-11 | D42166J | | 2 | | D04684 | B1 | | | 115-199 |
| 0077 | 16 | | GK | | 3-5 | 21-25-11 | D41746J | | 18 | | K00415 | C2 | E | * | 001-099 |
| 0077 | 16 | | GK | | 5-0 | 21-25-11 | D41746J | | 18 | | K00415 | C2 | E | * | 115-199 |
| 0079 | 24 | | GK | | 1-10 | 21-51-11 | K00415 | | 12 | C | GD01660 | DC.. | 2 | | 001-099 |
| 0079 | 24 | | GK | | 5-0 | 21-51-11 | K00415 | | 12 | C | GD01660 | DC.. | 2 | | 115-199 |
| 0080 | 24 | | GK | | 1-10 | 21-25-11 | K00415 | | 14 | C | GD01660 | DC.. | 2 | | 001-099 |
| 0080 | 24 | | GK | | 5-0 | 21-25-11 | K00415 | | 14 | C | GD01660 | DC.. | 2 | | 115-199 |
| 0081 | 24 | | GK | | 4-3 | 21-58-12 | D42074J | | 8 | | K00415 | 13 | C | * | 001-099 |
| 0081 | 24 | | GK | | 2-0 | 21-58-12 | D42074J | | 8 | | K00415 | 13 | C | * | 115-199 |
| 0082 | 24 | | GK | | 1-11 | 21-43-11 | D06912 | | A2 | | TB0155Y | C003 | BJ | | 001-099 |
| 0083 | 20 | | GK | | 1-8 | 21-43-11 | D06912 | | X2 | | GD01660 | AC.. | 2 | | 001-099 |
| 0084 | 20 | | GK | | 1-11 | 21-43-11 | D06912 | | X1 | | TB0155Y | C007 | BJ | | 001-099 |
| 0085 | 20 | | GA | | 1-4 | 24-51-14 | D42166J | | 6 | | K00119 | X1 | C | * | 001-099 |
| 0085 | 20 | | GA | | 2-0 | 24-51-14 | D42166J | | 6 | | K00119 | X1 | C | * | 115-199 |
| 0094 | 22 | | GA | | 2-2 | 21-25-11 | K00415 | | 13 | C | TB0155Y | A008 | BJ | | 001-099 |
| 0094 | 22 | | GA | | 5-0 | 21-25-11 | K00415 | | 13 | C | TB0155Y | A008 | BJ | | 115-199 |
| 0095 | 22 | | GA | | 3-11 | 21-25-11 | D41746J | | 10 | | TB0155Y | A008 | BJ | | 001-099 |
| 0095 | 22 | | GA | | 5-0 | 21-25-11 | TB0155Y | A008 | BJ | | D41746J | 10 | | | 115-199 |
| B-01 | | | | | 0-0 | 21-43-11 | TS5018 | | 1 | | TB0155Y | A003 | BJ | | 115-199 |
| B-02 | | | | | 0-0 | 21-43-11 | TS5018 | | 2 | | GD01660 | DC.. | 2 | | 115-199 |
| B-03 | | | | | 0-0 | 21-43-11 | TS5018 | | 3 | | TB0155X | D002 | BJ | | 115-199 |
| B-04 | | | | | 0-0 | 21-43-11 | TS5018 | | 4 | | TB0155Y | C003 | BJ | | 115-199 |
| B-05 | | | | | 0-0 | 21-43-11 | TS5018 | | 5 | | TB0155Y | CAP | Y | | 115-199 |
| W1252 | 286N1252 | | | P70 MODULE WIRING, CB PANEL | | | | | | | | | | | |
| 0001 | 12 | | HA | | 2-7 | 24-51-14 | C04001 | = B | D | | C01260 | = B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1252 | 286N1252 | | | P70 MODULE WIRING, CB PANEL (continued) | | | | | | | | | | | |
| 0001 | 12 | | HA | | 2-8 | 24-51-14 | C04001 | =B | D | | C01260 | =B | D | | 115-199 |
| 0002 | 12 | | HA | | 1-1 | 24-51-14 | C04341 | =B | D | * | C00663 | =B | D | * | 001-099 |
| 0002 | 12 | | HA | | 1-0 | 24-51-14 | C04002 | =B | D | * | C00663 | =B | D | * | 115-199 |
| 0003 | 12 | | HA | | 1-5 | 24-51-11 | C01125 | =B | D | | C00334 | C1 | D | * | 001-099 |
| 0003 | 12 | | HA | | 1-4 | 24-51-11 | C01125 | =B | D | | C00334 | C1 | D | * | 115-199 |
| 0004 | 12 | | HA | | 2-0 | 24-51-14 | C00662 | =B | D | * | C03002 | C1 | D | * | 001-099 |
| 0004 | 12 | | HA | | 1-11 | 24-51-14 | C00662 | =B | D | * | C03002 | C1 | D | * | 115-199 |
| 0005 | 10 | | HA | | 0-9 | 24-51-14 | C03002 | A1 | D | * | C03009 | A2 | D | * | 001-099 |
| 0005 | 10 | | HA | | 0-11 | 24-51-14 | C03002 | A1 | D | * | C03009 | A2 | D | * | 115-199 |
| 0006 | 12 | | HA | | 2-1 | 24-51-14 | C03002 | A1 | D | * | C01261 | =B | D | | ALL |
| 0007 | 10 | | HA | | 0-9 | 24-51-14 | C03002 | B1 | D | * | C03009 | B2 | D | * | 001-099 |
| 0007 | 10 | | HA | | 0-11 | 24-51-14 | C03002 | B1 | D | * | C03009 | B2 | D | * | 115-199 |
| 0008 | 12 | | HA | | 1-9 | 24-51-14 | C03002 | B1 | D | * | C04341 | =B | D | * | 001-099 |
| 0008 | 12 | | HA | | 1-8 | 24-51-14 | C03002 | B1 | D | * | C04002 | =B | D | * | 115-199 |
| 0009 | 10 | | HA | | 0-10 | 24-51-14 | C03002 | C1 | D | * | C03009 | C2 | D | * | 001-099 |
| 0009 | 10 | | HA | | 1-0 | 24-51-14 | C03002 | C1 | D | * | C03009 | C2 | D | * | 115-199 |
| 0010 | 12 | | HA | | 2-8 | 24-51-14 | C00663 | =B | D | * | C01259 | =B | D | | 001-099 |
| 0010 | 12 | | HA | | 2-9 | 24-51-14 | C00663 | =B | D | * | C01259 | =B | D | | 115-199 |
| 0011 | 12 | | HA | | 2-10 | 24-51-14 | C04002 | =B | D | * | C01292 | =B | D | * | 001-099 |
| 0011 | 12 | | HA | | 2-11 | 24-51-14 | C00662 | =B | D | * | C01292 | =B | D | | 115-199 |
| 0012 | 08 | | HA | | 1-7 | 24-51-11 | C00336 | A2 | D | * | C00391 | A2 | D | * | 001-099 |
| 0012 | 08 | | HA | | 1-0 | 24-51-11 | C00336 | A2 | D | * | C00391 | A2 | D | * | 115-199 |
| 0013 | 12 | | HA | | 1-0 | 24-51-11 | C03028 | A1 | D | * | C00336 | A2 | D | * | 115-199 |
| 0014 | 12 | | HA | | 2-7 | 24-51-11 | C00334 | A1 | D | | C00336 | A2 | D | * | 001-099 |
| 0014 | 12 | | HA | | 1-0 | 24-51-11 | C00334 | A1 | D | | C03028 | A1 | D | * | 115-199 |
| 0015 | 12 | | HA | | 1-8 | 24-51-11 | C00334 | B1 | D | | C00336 | B2 | D | * | 001-099 |
| 0015 | 12 | | HA | | 1-0 | 24-51-11 | C00334 | B1 | D | | C03028 | B1 | D | * | 115-199 |
| 0016 | 12 | | HA | | 1-4 | 24-51-11 | C03028 | B1 | D | * | C00336 | B2 | D | * | 115-199 |
| 0017 | 08 | | HA | | 4-8 | 24-51-14 | C03009 | C2 | D | * | K00119 | C2 | E | | 001-099 |
| 0017 | 08 | | HA | | 4-6 | 24-51-14 | C03009 | C2 | D | * | K00119 | C2 | E | | 115-199 |
| 0018 | 08 | | HA | | 1-2 | 24-51-11 | C00336 | B2 | D | * | C00391 | B2 | D | * | 001-099 |
| 0018 | 08 | | HA | | 1-0 | 24-51-11 | C00336 | B2 | D | * | C00391 | B2 | D | * | 115-199 |
| 0019 | 12 | | HA | | 1-8 | 24-51-11 | C00334 | C1 | D | * | C00336 | C2 | D | * | 001-099 |
| 0019 | 12 | | HA | | 1-0 | 24-51-11 | C00334 | C1 | D | * | C03028 | C1 | D | * | 115-199 |
| 0020 | 12 | | HA | | 1-4 | 24-51-11 | C03028 | C1 | D | * | C00336 | C2 | D | * | 115-199 |
| 0021 | 08 | | HA | | 1-1 | 24-51-11 | C00336 | C2 | D | * | C00391 | C2 | D | * | 001-099 |
| 0021 | 08 | | HA | | 1-0 | 24-51-11 | C00336 | C2 | D | * | C00391 | C2 | D | * | 115-199 |
| 0022 | 08 | | HA | | 2-10 | 24-51-11 | C00391 | C2 | D | * | TB5050 | 3 | E | | 001-099 |
| 0022 | 08 | | HA | | 2-8 | 24-51-11 | C00391 | C2 | D | * | TB5050 | 3 | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1252 | 286N1252 | | | P70 MODULE WIRING, CB PANEL (continued) | | | | | | | | | | | |
| 0023 | 08 | | HA | | 3-0 | 24-51-11 | C00391 | B2 | D | * | TB5050 | 2 | E | | 001-099 |
| 0023 | 08 | | HA | | 2-10 | 24-51-11 | C00391 | B2 | D | * | TB5050 | 2 | E | | 115-199 |
| 0024 | 08 | | HA | | 3-1 | 24-51-11 | C00391 | A2 | D | * | TB5050 | 1 | E | | 001-099 |
| 0024 | 08 | | HA | | 3-0 | 24-51-11 | C00391 | A2 | D | * | TB5050 | 1 | E | | 115-199 |
| 0025 | 08 | | HA | | 4-8 | 24-51-14 | C03009 | B2 | D | * | K00119 | B2 | E | | 001-099 |
| 0025 | 08 | | HA | | 4-7 | 24-51-14 | C03009 | B2 | D | * | K00119 | B2 | E | | 115-199 |
| 0026 | 08 | | HA | | 4-10 | 24-51-14 | C03009 | A2 | D | * | K00119 | A2 | E | | 001-099 |
| 0026 | 08 | | HA | | 4-8 | 24-51-14 | C03009 | A2 | D | * | K00119 | A2 | E | | 115-199 |
| 0030 | 16 | | GA | | 1-7 | 21-25-11 | C00336 | C1 | D | * | C04373 | =B | D | | 001-099 |
| 0030 | 16 | | GA | | 2-0 | 21-25-11 | C00336 | C1 | D | * | C04373 | =B | D | | 115-199 |
| 0031 | 24 | | GK | | 3-4 | 21-25-11 | C04373 | =L | D | | TB0155X | A002 | BJ | | 001-099 |
| 0031 | 24 | | GK | | 4-0 | 21-25-11 | C04373 | =L | D | | TB0155X | A002 | BJ | | 115-199 |
| 0034 | 10 | | HA | | 4-0 | 25-31-13 | C03023 | A1 | D | | TB5050 | 4 | E | | 115-199 |
| 0035 | 10 | | HA | | 4-0 | 25-31-13 | C03023 | B1 | D | | TB5050 | 5 | E | | 115-199 |
| 0036 | 10 | | HA | | 4-0 | 25-31-13 | C03023 | C1 | D | | TB5050 | 6 | E | | 115-199 |
| 0037 | 10 | | HA | | 4-0 | 25-31-27 | C03025 | A1 | D | | TB5050 | 7 | E | | 115-199 |
| 0038 | 10 | | HA | | 4-0 | 25-31-27 | C03025 | B1 | D | | TB5050 | 8 | E | | 115-199 |
| 0039 | 10 | | HA | | 4-0 | 25-31-27 | C03025 | C1 | D | | TB5050 | 9 | E | | 115-199 |
| 0040 | 08 | | HA | | 2-0 | 24-51-14 | C03025 | A2 | D | * | C03023 | A2 | D | | 115-199 |
| 0041 | 08 | | HA | | 2-0 | 24-51-14 | C03025 | B2 | D | * | C03023 | B2 | D | | 115-199 |
| 0042 | 08 | | HA | | 2-0 | 24-51-14 | C03025 | C2 | D | * | C03023 | C2 | D | | 115-199 |
| 0043 | 10 | | HA | | 4-0 | 24-51-14 | K10297 | A2 | E | | C03025 | A2 | D | * | 115-199 |
| 0044 | 10 | | HA | | 4-0 | 24-51-14 | K10297 | B2 | E | | C03025 | B2 | D | * | 115-199 |
| 0045 | 10 | | HA | | 4-0 | 24-51-14 | K10297 | C2 | E | | C03025 | C2 | D | * | 115-199 |
| 0046 | 12 | | HA | | 1-3 | 24-51-14 | C04203 | =B | D | | C01292 | =B | D | * | 001-099 |
| 0046 | 12 | | HA | | 2-2 | 24-51-14 | C04203 | =B | D | | C03009 | C2 | D | | 115-199 |
| 0047 | 20 | | GA | | 4-0 | 33-45-11 | C04203 | =L | D | | TB0155X | B001 | BJ | | ALL |
| 0048 | 20 | | GA | | 4-1 | 33-45-11 | C04204 | =L | D | | TB0155Y | A004 | BJ | | 001-099 |
| 0048 | 20 | | GA | | 5-0 | 33-45-11 | C04204 | =L | D | | TB0155Y | A004 | BJ | | 115-199 |
| 0066 | 20 | | GA | | 3-7 | 38-13-11 | C04002 | =L | D | | D41968J | 21 | | | 001-099 |
| 0068 | 12 | | HA | | 1-0 | 24-51-14 | C00662 | =B | D | * | C04002 | =B | D | * | 001-099 |
| 0090 | 24 | | GK | | 3-1 | 26-16-21 | C00063 | =B | D | | D41968J | 5 | | | 001-099 |
| 0090 | 24 | | GK | | 4-0 | 26-16-21 | C00063 | =B | D | | D41968J | 5 | | | 115-199 |
| 0091 | 24 | | GK | | 3-2 | 26-16-21 | C00062 | =B | D | | D41968J | 6 | | | 001-099 |
| 0091 | 24 | | GK | | 4-0 | 26-16-21 | C00062 | =B | D | | D41968J | 6 | | | 115-199 |
| 0092 | 24 | | GK | | 3-3 | 26-16-21 | C00061 | =B | D | | D41968J | 7 | | | 001-099 |
| 0092 | 24 | | GK | | 4-0 | 26-16-21 | C00061 | =B | D | | D41968J | 7 | | | 115-199 |
| 0093 | 24 | | GK | | 3-4 | 26-16-21 | C00060 | =B | D | | D41968J | 8 | | | 001-099 |
| 0093 | 24 | | GK | | 4-0 | 26-16-21 | C00060 | =B | D | | D41968J | 8 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1252 | 286N1252 | | | P70 MODULE WIRING, CB PANEL (continued) | | | | | | | | | | | |
| 0101 | 20 | | GA | | 3-4 | 33-23-11 | C01259 | =L | D | | D41880J | 1 | | | 001-099 |
| 0101 | 20 | | GA | | 4-0 | 33-23-11 | C01259 | =L | D | | D41880J | 1 | | | 115-199 |
| 0102 | 20 | | GA | | 3-6 | 33-23-12 | C01260 | =L | D | | D41880J | 2 | | | 001-099 |
| 0102 | 20 | | GA | | 4-0 | 33-23-12 | C01260 | =L | D | | D41880J | 2 | | | 115-199 |
| 0103 | 20 | | GA | | 3-6 | 33-23-13 | C01261 | =L | D | | D41880J | 3 | | | 001-099 |
| 0103 | 20 | | GA | | 4-0 | 33-23-13 | C01261 | =L | D | | D41880J | 3 | | | 115-199 |
| 0104 | 20 | | GA | | 3-5 | 33-23-14 | C01292 | =L | D | | D41880J | 4 | | | 001-099 |
| 0104 | 20 | | GA | | 4-0 | 33-23-14 | C01292 | =L | D | | D41880J | 4 | | | 115-199 |
| 0105 | 20 | | GA | | 3-9 | 21-45-11 | C00662 | =L | D | | D41880J | 5 | | | 001-099 |
| 0105 | 20 | | GA | | 4-0 | 21-45-11 | C00662 | =L | D | | D41880J | 5 | | | 115-199 |
| 0106 | 20 | | GA | | 3-9 | 21-45-11 | C00663 | =L | D | | D41880J | 6 | | | 001-099 |
| 0106 | 20 | | GA | | 4-0 | 21-45-11 | C00663 | =L | D | | D41880J | 6 | | | 115-199 |
| 0107 | 20 | | GA | | 3-6 | 30-41-11 | C01127 | =L | D | | D41754J | 7 | | | 001-099 |
| 0107 | 20 | | GA | | 4-0 | 30-41-11 | C01127 | =L | D | | D41754J | 7 | | | 115-199 |
| 0108 | 20 | | GA | | 3-6 | 30-41-11 | C01125 | =L | D | | D41754J | 8 | | | 001-099 |
| 0108 | 20 | | GA | | 4-0 | 30-41-11 | C01125 | =L | D | | D41754J | 8 | | | 115-199 |
| 0109 | 20 | | GA | | 4-11 | 21-43-11 | C03002 | A2 | D | | K10057 | A2 | D | | 001-099 |
| 0109 | 20 | | GA | | 5-0 | 21-43-11 | C03002 | A2 | D | | K10057 | A2 | D | | 115-199 |
| 0110 | 22 | | GA | | 4-0 | 21-58-24 | C03028 | A2 | D | | D41880J | 7 | | | 115-199 |
| 0111 | 22 | | GA | | 4-0 | 21-58-24 | C03028 | B2 | D | | D41880J | 8 | | | 115-199 |
| 0112 | 22 | | GA | | 4-0 | 21-58-24 | C03028 | C2 | D | | D41880J | 9 | | | 115-199 |
| 0113 | 18 | | GA | | 3-8 | 21-58-21 | C00334 | A2 | D | | D41754J | 3 | | | 001-099 |
| 0113 | 18 | | GA | | 4-0 | 21-58-21 | C00334 | A2 | D | | D41754J | 3 | | | 115-199 |
| 0114 | 18 | | GA | | 3-7 | 21-58-21 | C00334 | B2 | D | | D41754J | 4 | | | 001-099 |
| 0114 | 18 | | GA | | 4-0 | 21-58-21 | C00334 | B2 | D | | D41754J | 4 | | | 115-199 |
| 0115 | 18 | | GA | | 3-7 | 21-58-21 | C00334 | C2 | D | | D41754J | 5 | | | 001-099 |
| 0115 | 18 | | GA | | 4-0 | 21-58-21 | C00334 | C2 | D | | D41754J | 5 | | | 115-199 |
| 0116 | 14 | | GA | | 3-7 | 21-25-11 | C00336 | A1 | D | | K00415 | A1 | E | | 001-099 |
| 0116 | 14 | | GA | | 4-0 | 21-25-11 | C00336 | A1 | D | | K00415 | A1 | E | | 115-199 |
| 0117 | 14 | | GA | | 4-2 | 21-44-11 | C03009 | A1 | D | | K10083 | A1 | E | | 001-099 |
| 0117 | 14 | | GA | | 5-0 | 21-44-11 | C03009 | A1 | D | | K10083 | A1 | E | | 115-199 |
| 0118 | 14 | | GA | | 3-5 | 21-25-11 | C00336 | C1 | D | * | K00415 | C1 | E | | 001-099 |
| 0118 | 14 | | GA | | 4-0 | 21-25-11 | C00336 | C1 | D | * | K00415 | C1 | E | | 115-199 |
| 0119 | 14 | | GA | | 3-6 | 21-25-11 | C00336 | B1 | D | | K00415 | B1 | E | | 001-099 |
| 0119 | 14 | | GA | | 4-0 | 21-25-11 | C00336 | B1 | D | | K00415 | B1 | E | | 115-199 |
| 0120 | 14 | | GA | | 4-0 | 21-44-11 | C03009 | C1 | D | | K10083 | C1 | E | | ALL |
| 0121 | 14 | | GA | | 4-1 | 21-44-11 | C03009 | B1 | D | | K10083 | B1 | E | | 001-099 |
| 0121 | 14 | | GA | | 4-0 | 21-44-11 | C03009 | B1 | D | | K10083 | B1 | E | | 115-199 |
| 0122 | 20 | | GA | | 4-11 | 21-43-11 | C03002 | B2 | D | | K10057 | B2 | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|------|---------|--------|----|-------------|------------------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1252 | 286N1252 | | | | P70 MODULE WIRING, CB PANEL (continued) | | | | | | | | | | | | |
| 0122 | 20 | | GA | | 5-0 | 21-43-11 | | C03002 | | B2 | D | | K10057 | B2 | D | | 115-199 |
| 0123 | 20 | | GA | | 4-10 | 21-43-11 | | C03002 | | C2 | D | | K10057 | C2 | D | | 001-099 |
| 0123 | 20 | | GA | | 5-0 | 21-43-11 | | C03002 | | C2 | D | | K10057 | C2 | D | | 115-199 |
| 0124 | 22 | | GA | | 3-11 | 38-13-11 | | C04001 | | =L | D | | D41968J | 11 | | | 001-099 |
| 0124 | 20 | | GA | | 4-0 | 38-13-11 | | C04001 | | =L | D | | D41968J | 11 | | | 115-199 |
| 0125 | 22 | | GA | | 3-11 | 38-13-11 | | C04341 | | =L | D | | D41968J | 12 | | | 001-099 |
| 0125 | 20 | | GA | | 4-0 | 38-13-11 | | C04002 | | =L | D | | D41968J | 12 | | | 115-199 |
| 0201 | 24 | | GK | | 3-1 | 26-16-21 | | C00063 | | =L | D | | D41968J | 1 | | | 001-099 |
| 0201 | 24 | | GK | | 3-0 | 26-16-21 | | C00063 | | =L | D | | D41968J | 1 | | | 115-199 |
| 0202 | 24 | | GK | | 3-2 | 26-16-21 | | C00062 | | =L | D | | D41968J | 2 | | | 001-099 |
| 0202 | 24 | | GK | | 4-0 | 26-16-21 | | C00062 | | =L | D | | D41968J | 2 | | | 115-199 |
| 0203 | 24 | | GK | | 3-2 | 26-16-21 | | C00061 | | =L | D | | D41968J | 3 | | | 001-099 |
| 0203 | 24 | | GK | | 4-0 | 26-16-21 | | C00061 | | =L | D | | D41968J | 3 | | | 115-199 |
| 0204 | 24 | | GK | | 3-3 | 26-16-21 | | C00060 | | =L | D | | D41968J | 4 | | | 001-099 |
| 0204 | 24 | | GK | | 4-0 | 26-16-21 | | C00060 | | =L | D | | D41968J | 4 | | | 115-199 |
| 0301 | 20 | | GA | | 3-10 | 28-26-11 | | C00070 | | =B | D | | D42074J | 14 | | | 001-099 |
| 0301 | 20 | | GA | | 4-0 | 28-26-11 | | C00070 | | =B | D | | D42074J | 14 | | | 115-199 |
| 0302 | 22 | | GA | | 3-10 | 28-26-11 | | C00070 | | =L | D | | D42074J | 17 | | | 001-099 |
| 0302 | 22 | | GA | | 4-0 | 28-26-11 | | C00070 | | =L | D | | D42074J | 17 | | | 115-199 |
| 0303 | 20 | | GA | | 3-9 | 28-26-11 | | C00071 | | =B | D | | D42074J | 15 | | | 001-099 |
| 0303 | 20 | | GA | | 4-0 | 28-26-11 | | C00071 | | =B | D | | D42074J | 15 | | | 115-199 |
| 0304 | 22 | | GA | | 3-9 | 28-26-11 | | C00071 | | =L | D | | D42074J | 16 | | | 001-099 |
| 0304 | 22 | | GA | | 4-0 | 28-26-11 | | C00071 | | =L | D | | D42074J | 16 | | | 115-199 |
| 2001B | 12 | | HB | AA | 3-2 | 30-41-11 | | C00391 | | B1 | D | | D41754J | 1 | | | 001-099 |
| 2001B | 12 | | HB | AA | 4-0 | 30-41-11 | | C00391 | | B1 | D | | D41754J | 1 | | | 115-199 |
| 2001R | 12 | | HB | AA | 0-0 | 30-41-11 | | C00391 | | A1 | D | | D41754J | 2 | | | ALL |
| ZZAA | 02 | | ZB | | 0-0 | 24-51-14 | | C01260 | | =B | D | | C01261 | =B | D | | ALL |
| ZZBB | 02 | | ZB | | 0-0 | 24-51-11 | | C01125 | | =B | D | | C01127 | =B | D | | ALL |
| ZZCC | 02 | | ZB | | 0-0 | 24-51-14 | | C04204 | | =B | D | | C04203 | =B | D | | ALL |
| W1254 | 286N1254 | | | | P71 HYDRAULIC GENERATOR CONTROL PANEL | | | | | | | | | | | | |
| 0001 | 22 | | HA | | 4-0 | 24-25-11 | | D40270J | | 2 | | | TB0103Y | C002 | BJ | | 001-002 |
| 0001 | 22 | | HA | | 3-0 | 24-25-11 | | D40270J | | 2 | | | TB0103Y | C002 | BJ | | 115-199 |
| 0002 | 22 | | HA | | 3-0 | 24-25-11 | | D07060 | | B1 | | | TB0103Y | C002 | BJ | | 001-002 |
| 0002 | 22 | | HA | | 2-0 | 24-25-11 | | D07060 | | B1 | | | TB0103Y | C002 | BJ | | 115-199 |
| 0003 | 22 | | HA | | 4-0 | 24-25-11 | | D40270J | | 1 | | | D07060 | A3 | | | 001-002 |
| 0003 | 22 | | HA | | 3-0 | 24-25-11 | | D40270J | | 1 | | | D07060 | A3 | | | 115-199 |
| 0004 | 20 | | HA | | 4-0 | 24-25-11 | | D40460J | | 9 | | | D07060 | X1 | | | 001-002, 115-199 |
| 0005 | 20 | | HA | | 2-0 | 24-25-11 | | D07060 | | X2 | | | GD03144 | AC.. | E | | 001-002, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|--------|---------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1254 | 286N1254 | | | P71 HYDRAULIC GENERATOR CONTROL PANEL (continued) | | | | | | | | | | | |
| 0006 | 22 | | HA | | 4-0 | 24-25-11 | D40416J | | 1 | | D07058 | | X1 | | 001-002 |
| 0006 | 22 | | HA | | 3-0 | 24-25-11 | D40416J | | 1 | | D07058 | | X1 | | 115-199 |
| 0007 | 22 | | HA | | 3-0 | 24-25-11 | TB0103Y | | C002 | BJ | K10565 | | 12 | C | 001-002 |
| 0007 | 22 | | HA | | 4-0 | 24-25-11 | TB0103Y | | C002 | BJ | K10565 | | 12 | C | 115-199 |
| 0008 | 22 | | HA | | 4-0 | 24-25-11 | K10565 | | X1 | C | * | D07062 | | A2 | 001-002, 115-199 |
| 0009 | 22 | | HA | | 2-0 | 24-25-11 | K10565 | | X1 | C | * | K10566 | | X1 | ALL |
| 0010 | 20 | | GA | | 3-0 | 24-25-11 | K10565 | | X2 | C | | GD04002 | | DC.. | ALL |
| 0011 | 22 | | HA | | 2-0 | 24-25-11 | D07060 | | B2 | | | D07058 | | B2 | 001-002 |
| 0011 | 22 | | HA | | 1-0 | 24-25-11 | D07060 | | B2 | | | D07058 | | B2 | 115-199 |
| 0012 | 22 | | HA | | 2-0 | 24-25-11 | D07060 | | A2 | | | D07058 | | A2 | 001-002 |
| 0012 | 22 | | HA | | 3-0 | 24-25-11 | D07060 | | A2 | | | D07058 | | A2 | 115-199 |
| 0013 | 20 | | HA | | 2-0 | 24-25-11 | D07058 | | X2 | | | GD03144 | | AC.. | 001-002, 115-199 |
| 0014 | 22 | | HA | | 3-0 | 24-25-11 | D07064 | | 2 | | | D07070 | | 9 | 001-002, 115-199 |
| 0015 | 22 | | HA | | 2-0 | 24-25-11 | D07064 | | 7 | | | TB0103Y | | C003 | 001-002, 115-199 |
| 0016 | 22 | | HA | | 4-0 | 24-25-11 | D07064 | | 3 | | | K10564 | | 13 | 001-002 |
| 0016 | 22 | | HA | | 3-0 | 24-25-11 | D07064 | | 3 | | | K10564 | | 13 | 115-199 |
| 0017 | 20 | | GA | | 4-0 | 24-25-11 | K10564 | | X2 | C | | GD04002 | | DC.. | 001-002 |
| 0017 | 20 | | GA | | 3-0 | 24-25-11 | K10564 | | X2 | C | | GD04002 | | DC.. | 115-199 |
| 0018 | 22 | | HA | | 2-0 | 24-25-11 | K10566 | | X1 | C | * | K10567 | | X1 | ALL |
| 0019 | 20 | | GA | | 2-0 | 24-25-11 | K10566 | | X2 | C | | GD04002 | | DC.. | 001-002 |
| 0019 | 20 | | GA | | 3-0 | 24-25-11 | K10566 | | X2 | C | | GD04002 | | DC.. | 003-099, 115-199 |
| 0020 | 22 | | HA | | 4-0 | 24-25-11 | K10564 | | X1 | C | | K10567 | | X1 | 001-002 |
| 0020 | 22 | | HA | | 3-0 | 24-25-11 | K10564 | | X1 | C | | K10567 | | X1 | 115-199 |
| 0021 | 20 | | GA | | 3-0 | 24-25-11 | K10567 | | X2 | C | | GD04002 | | DC.. | 001-002 |
| 0021 | 20 | | GA | | 2-0 | 24-25-11 | K10567 | | X2 | C | | GD04002 | | DC.. | 003-099, 115-199 |
| 0022 | 20 | | GA | | 4-0 | 24-25-11 | K10564 | | 12 | C | | GD04002 | | DC.. | 001-002 |
| 0022 | 20 | | GA | | 3-0 | 24-25-11 | K10564 | | 12 | C | | GD04002 | | DC.. | 115-199 |
| 0023 | 22 | | GA | | 2-0 | 24-25-11 | D07062 | | Y2 | | | GD04002 | | DC.. | 001-002, 115-199 |
| 0024 | 22 | | HA | | 2-0 | 24-25-11 | TB0103Y | | C002 | BJ | | D07062 | | B2 | 001-002, 115-199 |
| 0025 | 22 | | HA | | 2-0 | 24-25-11 | D07062 | | B3 | | | TB0103Y | | C001 | 001-002, 115-199 |
| 0026 | 22 | | HA | | 4-0 | 24-25-11 | TB0103Y | | C003 | BJ | | D40450J | | 1 | 001-002, 115-199 |
| 0027 | 22 | | HA | | 2-0 | 24-25-11 | M10663 | | B | C | | D07062 | | Y1 | 001-002, 115-199 |
| 0028 | 22 | | HA | | 2-0 | 24-25-11 | D07058 | | B1 | | | M10663 | | A | 001-002, 115-199 |
| 0029 | 22 | | HA | | 2-0 | 24-25-11 | D07058 | | A3 | | | M10664 | | A | 001-002, 115-199 |
| 0030 | 22 | | HA | | 2-0 | 24-25-11 | M10664 | | B | C | | D07062 | | X1 | 001-002 |
| 0030 | 22 | | HA | | 3-0 | 24-25-11 | M10664 | | B | C | | D07062 | | X1 | 115-199 |
| 0031 | 22 | | GA | | 2-0 | 24-25-11 | D07062 | | X2 | | | GD04002 | | DC.. | 001-002 |
| 0031 | 22 | | GA | | 3-0 | 24-25-11 | D07062 | | X2 | | | GD04002 | | DC.. | 115-199 |
| 0032 | 22 | | HA | | 3-0 | 24-25-11 | D07062 | | A1 | | | D07070 | | 14 | 001-002, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1254 | 286N1254 | | | P71 HYDRAULIC GENERATOR CONTROL PANEL (continued) | | | | | | | | | | | |
| 0033 | 22 | | HA | | 3-0 | 24-25-11 | D07070 | 10 | | | D07064 | 4 | | | 001-002, 115-199 |
| 0034 | 20 | | GA | | 3-0 | 24-25-11 | D07070 | 20 | | | GD04002 | DC.. | 2 | | 001-002, 115-199 |
| 0035 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | | | AC | GD03148 | ST.. | E | | 001-002, 115-199 |
| 0036 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | 6 | | | K10565 | A1 | E | | 001-002 |
| 0036 | 20 | | HA | | 4-0 | 24-25-12 | D07070 | 6 | | | K10565 | A1 | E | | 115-199 |
| 0037 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | 7 | | | K10565 | B1 | E | | 001-002 |
| 0037 | 20 | | HA | | 4-0 | 24-25-12 | D07070 | 7 | | | K10565 | B1 | E | | 115-199 |
| 0038 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | 8 | | | K10565 | C1 | E | | 001-002 |
| 0038 | 20 | | HA | | 4-0 | 24-25-12 | D07070 | 8 | | | K10565 | C1 | E | | 115-199 |
| 0039 | 12 | | HA | | 4-0 | 24-25-12 | K10565 | A1 | E | * | D40418J | 1 | | | 001-002 |
| 0039 | 12 | | HA | | 3-0 | 24-25-12 | K10565 | A1 | E | * | D40418J | 1 | | | 115-199 |
| 0040 | 12 | | HA | | 4-0 | 24-25-12 | K10565 | B1 | E | * | D40418J | 2 | | | 001-002 |
| 0040 | 12 | | HA | | 3-0 | 24-25-12 | K10565 | B1 | E | * | D40418J | 2 | | | 115-199 |
| 0041 | 12 | | HA | | 4-0 | 24-25-12 | K10565 | C1 | E | * | D40418J | 3 | | | 001-002 |
| 0041 | 12 | | HA | | 3-0 | 24-25-12 | K10565 | C1 | E | * | D40418J | 3 | | | 115-199 |
| 0042 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | 17 | | | GD03144 | AC.. | E | | 001-002, 115-199 |
| 0043 | 20 | | GA | | 3-0 | 24-25-12 | D07070 | 13 | | | GD04002 | DC.. | 2 | | 001-002, 115-199 |
| 0045 | 12 | | HA | | 2-0 | 24-25-12 | K10565 | C1 | E | * | K10566 | C1 | E | * | 001-002, 115-199 |
| 0047 | 12 | | HA | | 2-0 | 24-25-12 | K10565 | B1 | E | * | K10566 | B1 | E | * | 001-002, 115-199 |
| 0049 | 12 | | HA | | 2-0 | 24-25-12 | K10565 | A1 | E | * | K10566 | A1 | E | * | 001-002, 115-199 |
| 0050 | 12 | | HA | | 2-0 | 24-25-12 | K10566 | C1 | E | * | K10567 | C1 | E | | 001-002, 115-199 |
| 0051 | 12 | | HA | | 2-0 | 24-25-12 | K10566 | B1 | E | * | K10567 | B1 | E | * | 001-002, 115-199 |
| 0052 | 12 | | HA | | 2-0 | 24-25-12 | K10566 | A1 | E | * | K10567 | A1 | E | | 001-002, 115-199 |
| 0053 | 10 | | HA | | 3-0 | 24-25-13 | K10564 | A1 | F | * | C04350 | =B | D | * | 001-002, 115-199 |
| 0054 | 12 | | HA | | 3-0 | 24-25-13 | K10567 | B1 | E | * | C04351 | =B | D | | 001-002, 115-199 |
| 0054 | 12 | | HA | | 2-7 | 24-25-13 | K10567 | B1 | E | * | C04351 | =B | D | | 003-099 |
| 0055 | 22 | | HA | | 4-0 | 24-25-13 | K10565 | 11 | C | | D40270J | 5 | | | 001-002, 115-199 |
| 0055 | 24 | | GK | | 3-0 | 24-25-13 | K10565 | 11 | C | | D40270J | 5 | | | 003-099 |
| 0056 | 22 | | HA | | 4-0 | 24-25-13 | C04350 | =L | D | | D40270J | 3 | | | 001-002 |
| 0056 | 22 | | HA | | 5-0 | 24-25-13 | C04350 | CAP | Y | | D40270J | 3 | | | 115-199 |
| 0057 | 22 | | HA | | 4-0 | 24-25-13 | C04351 | =L | D | | D40270J | 4 | | | 001-002 |
| 0057 | 24 | | GK | | 4-0 | 24-25-13 | C04351 | =L | D | | D40270J | 4 | | | 003-099 |
| 0057 | 22 | | HA | | 5-0 | 24-25-13 | C04351 | CAP | Y | | D40270J | 4 | | | 115-199 |
| 0058 | 22 | | HA | | 2-0 | 24-25-13 | D40270J | 6 | | | D40450J | 12 | | | 001-099 |
| 0058 | 22 | | HA | | 3-0 | 24-25-13 | D40270J | 6 | | | D40450J | 12 | | | 115-199 |
| 0059 | 18 | | HA | | 3-0 | 24-51-25 | D40460J | 1 | | | K10567 | A3 | E | | 001-002, 115-199 |
| 0059 | 12 | | HA | | 2-4 | 24-51-25 | D40460J | 1 | | | K10567 | A3 | E | | 003-099 |
| 0060 | 18 | | HA | | 3-0 | 24-51-25 | D40460J | 2 | | | K10567 | B3 | E | | 001-002, 115-199 |
| 0060 | 12 | | HA | | 2-4 | 24-51-25 | D40460J | 2 | | | K10567 | B3 | E | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 10

Oct 09/2008



WIRE LIST
D280N032

Section W1250
Page 11
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1254 | 286N1254 | | | P71 HYDRAULIC GENERATOR CONTROL PANEL (continued) | | | | | | | | | | | |
| 0082 | 22 | | HA | | 4-0 | 34-22-81 | D40416J | 6 | | | K10566 | 12 | C | | 001-002 |
| 0082 | 22 | | HA | | 3-0 | 34-22-81 | D40416J | 6 | | | K10566 | 12 | C | | 003-099 |
| 0082 | 22 | | HA | | 4-0 | 34-22-83 | D40416J | 6 | | | K10566 | 12 | C | | 115-199 |
| 0083 | 20 | | GA | | 3-0 | 34-22-81 | K10566 | 11 | C | | GD04002 | DC.. | 2 | | ALL |
| 0084 | 10 | | HA | | 3-0 | 24-25-13 | K10564 | A1 | F | * | C04350 | =B | D | * | 001-002, 115-199 |
| 0085 | 22 | | HA | | 2-0 | 24-25-11 | K10565 | 13 | C | | D40270J | 8 | | | 001-002, 115-199 |
| 0102 | 22 | | HA | | 3-0 | 24-25-11 | D07070 | 10 | | | D40450J | 2 | | | 003-099 |
| 0103 | 22 | | HA | | 3-0 | 24-25-11 | D07070 | 9 | | | D40450J | 1 | | | 003-099 |
| 0104 | 22 | | HA | | 3-0 | 24-25-11 | D40270J | 1 | | | TB0103Y | A001 | BJ | | 003-099 |
| 0105 | 22 | | HA | | 3-0 | 24-25-11 | D07070 | 21 | | | TB0103Y | A001 | BJ | | 003-099 |
| 0107 | 22 | | HA | | 3-0 | 24-25-11 | D07070 | 13 | | | D40270J | 2 | | | 003-099 |
| 0108 | 22 | | HA | | 3-0 | 24-25-11 | D40270J | 7 | | | TB0103Y | A001 | BJ | | 003-099 |
| 0110 | 22 | | HA | | 3-0 | 24-25-11 | D07070 | 5 | | | D40460J | 9 | | | 003-099 |
| 0111 | 22 | | HA | | 3-0 | 24-25-11 | D07070 | 20 | | | D40416J | 1 | | | 003-099 |
| 0112 | 22 | | HA | | 4-0 | 24-25-11 | K10565 | 12 | C | | TB0103Y | A001 | BJ | | 003-099 |
| 0113 | 22 | | HA | | 2-0 | 24-25-11 | K10565 | 13 | C | | D40270J | 3 | | | 003-099 |
| 0114 | 20 | | HA | | 2-0 | 24-25-11 | D01925 | X2 | | | GD04002 | DC.. | 2 | | 003-099 |
| 0115 | 20 | | HA | | 2-0 | 24-25-11 | D07660 | X2 | | | GD04002 | DC.. | 2 | | 003-099 |
| 0116 | 22 | | HA | | 2-0 | 24-25-11 | D01925 | X1 | | | D07660 | X1 | | * | 003-099 |
| 0117 | 22 | | HA | | 3-0 | 24-25-11 | K10567 | X1 | C | * | D07660 | X1 | | * | 003-099 |
| 0118 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | 23 | | | D40450J | 11 | | | 003-099 |
| 0119 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | 17 | | | GD04002 | AC.. | 2 | | 003-099 |
| 0120 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | 12 | | | GD04002 | ST.. | 2 | | 003-099 |
| 0121 | 20 | | HA | | 4-0 | 24-25-12 | D07070 | 6 | | | C03060 | A1 | D | | 003-099 |
| 0122 | 20 | | HA | | 4-0 | 24-25-12 | D07070 | 7 | | | C03060 | B1 | D | | 003-099 |
| 0123 | 20 | | HA | | 4-0 | 24-25-12 | D07070 | 8 | | | C03060 | C1 | D | | 003-099 |
| 0124 | 12 | | HA | | 2-1 | 24-25-12 | C03060 | C2 | D | | K10565 | C1 | E | | 003-099 |
| 0125 | 12 | | HA | | 2-1 | 24-25-12 | C03060 | B2 | D | | K10565 | B1 | E | | 003-099 |
| 0126 | 12 | | HA | | 2-1 | 24-25-12 | C03060 | A2 | D | | K10565 | A1 | E | | 003-099 |
| 0127 | 12 | | HA | | 4-0 | 24-25-12 | C03060 | C1 | D | * | D40418J | 3 | | | 003-099 |
| 0128 | 12 | | HA | | 4-0 | 24-25-12 | C03060 | B1 | D | * | D40418J | 2 | | | 003-099 |
| 0129 | 12 | | HA | | 4-0 | 24-25-12 | C03060 | A1 | D | * | D40418J | 1 | | | 003-099 |
| 0130 | 12 | | HA | | 1-6 | 24-25-12 | C03060 | C1 | D | * | C03058 | C1 | D | * | 003-099 |
| 0131 | 12 | | HA | | 1-6 | 24-25-12 | C03060 | B1 | D | * | C03058 | B1 | D | * | 003-099 |
| 0132 | 12 | | HA | | 1-6 | 24-25-12 | C03060 | A1 | D | * | C03058 | A1 | D | * | 003-099 |
| 0133 | 12 | | HA | | 2-6 | 24-25-12 | C03058 | A2 | D | | K10566 | A1 | E | | 003-099 |
| 0134 | 12 | | HA | | 2-6 | 24-25-12 | C03058 | B2 | D | | K10566 | B1 | E | | 003-099 |
| 0135 | 12 | | HA | | 2-6 | 24-25-12 | C03058 | C2 | D | | K10566 | C1 | E | | 003-099 |
| 0136 | 12 | | HA | | 2-10 | 24-25-12 | C03059 | C2 | D | | K10567 | C1 | E | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1254 | 286N1254 | | | P71 HYDRAULIC GENERATOR CONTROL PANEL (continued) | | | | | | | | | | | |
| 0137 | 12 | | HA | | 2-10 | 24-25-12 | C03059 | B2 | D | | K10567 | B1 | E | * | 003-099 |
| 0138 | 12 | | HA | | 2-10 | 24-25-12 | C03059 | A2 | D | | K10567 | A1 | E | | 003-099 |
| 0139 | 12 | | HA | | 1-5 | 24-25-12 | C03059 | C1 | D | * | C03058 | C1 | D | * | 003-099 |
| 0140 | 12 | | HA | | 1-5 | 24-25-12 | C03059 | B1 | D | * | C03058 | B1 | D | * | 003-099 |
| 0141 | 12 | | HA | | 1-5 | 24-25-12 | C03059 | A1 | D | * | C03058 | A1 | D | * | 003-099 |
| 0142 | 12 | | HA | | 1-9 | 24-25-12 | C03059 | C1 | D | * | C03061 | C1 | D | | 003-099 |
| 0143 | 12 | | HA | | 1-8 | 24-25-12 | C03059 | B1 | D | * | C03061 | B1 | D | | 003-099 |
| 0144 | 12 | | HA | | 1-8 | 24-25-12 | C03059 | A1 | D | * | C03061 | A1 | D | | 003-099 |
| 0145 | 20 | | HA | | 4-0 | 24-25-12 | C03061 | C2 | D | | D41390J | 1 | | | 003-099 |
| 0146 | 20 | | HA | | 4-0 | 24-25-12 | C03061 | B2 | D | | D41390J | 2 | | | 003-099 |
| 0147 | 20 | | HA | | 4-0 | 24-25-12 | C03061 | A2 | D | | D41390J | 3 | | | 003-099 |
| 0151 | 24 | | GK | | 3-0 | 24-25-13 | D07660 | A1 | | | D40270J | 15 | | | 003-099 |
| 0152 | 20 | | HA | | 3-0 | 24-31-11 | D07660 | A2 | | | D40270J | 16 | | | 003-099 |
| 0153 | 18 | | HA | | 3-0 | 28-22-11 | D01925 | A2 | | | D40460J | 10 | | | 003-099 |
| 0154 | 18 | | HA | | 3-0 | 28-22-11 | D01925 | A1 | | | D40460J | 11 | | | 003-099 |
| 0155 | 22 | | HA | | 3-0 | 24-25-11 | D07070 | 14 | | | K10565 | X1 | C | * | 003-099 |
| 0160 | 20 | | HA | | 3-0 | 24-25-12 | D07070 | 18 | | | GD04002 | DC.. | 2 | | 003-099 |
| 2501B | 20 | | HF | AC | 3-0 | 24-25-12 | D07070 | 4 | | | D40450J | 10 | | | 001-002, 115-199 |
| 2501R | 20 | | HF | AC | 0-0 | 24-25-12 | D07070 | 5 | | | D40450J | 11 | | | 001-002, 115-199 |
| 2501Z | | | | AC | 0-0 | 24-25-12 | D07070 | | | AC | D40450J | 13 | | | 001-002, 115-199 |
| 2502B | 20 | | HF | AE | 3-0 | 24-25-12 | D07070 | 16 | | | D40450J | 9 | | | 003-099 |
| 2502R | 20 | | HF | AE | 0-0 | 24-25-12 | D07070 | 15 | | | D40450J | 8 | | | 003-099 |
| 2502Z | | | | AE | 0-0 | 24-25-12 | D07070 | | | AF | D40450J | 10 | | | 003-099 |
| 2503B | 20 | | HF | AG | 3-0 | 24-25-12 | D07070 | 24 | | | D40450J | 14 | | | 003-099 |
| 2503R | 20 | | HF | AG | 0-0 | 24-25-12 | D07070 | 4 | | | D40450J | 13 | | | 003-099 |
| 2503Z | | | | AG | 0-0 | 24-25-12 | D07070 | | | AF | D40450J | 15 | | | 003-099 |
| 3001B | 20 | | HC | AA | 3-0 | 24-25-12 | D07070 | 16 | | | D40450J | 5 | | | 001-002, 115-199 |
| 3001R | 20 | | HC | AA | 0-0 | 24-25-12 | D07070 | 15 | | | D40450J | 4 | | | 001-002, 115-199 |
| 3001Y | 20 | | HC | AA | 0-0 | 24-25-12 | D07070 | 11 | | | D40450J | 6 | | | 001-002, 115-199 |
| 3002B | 20 | | HC | AB | 3-0 | 24-25-12 | D07070 | 3 | | | D40450J | 7 | | | 001-002, 115-199 |
| 3002R | 20 | | HC | AB | 0-0 | 24-25-12 | D07070 | 1 | | | D40450J | 8 | | | 001-002, 115-199 |
| 3002Y | 20 | | HC | AB | 0-0 | 24-25-12 | D07070 | 2 | | | D40450J | 9 | | | 001-002, 115-199 |
| 3501B | 20 | | HG | AF | 3-0 | 24-25-12 | D07070 | 2 | | | D40450J | 5 | | | 003-099 |
| 3501R | 20 | | HG | AF | 0-0 | 24-25-12 | D07070 | 1 | | | D40450J | 4 | | | 003-099 |
| 3501Y | 20 | | HG | AF | 0-0 | 24-25-12 | D07070 | 3 | | | D40450J | 6 | | | 003-099 |
| 3501Z | | | | AF | 0-0 | 24-25-12 | D07070 | | | AF | D40450J | 7 | | | 003-099 |
| FRAC | | | | | 0-0 | 24-25-12 | D07070 | | | AC | D07070 | 12 | | | 001-002, 115-199 |
| FRAF | | | | | 0-0 | 24-25-12 | GD04002 | ST.. | 2 | | D07070 | | | AF | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W1250

Page 13 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) | | | | | | | | | | | |
| 0001 | 24 | | GK | | 3-0 | 21-31-11 | D41473J | 21 | | | D41713J | 9 | | | 001-099 |
| 0001 | 24 | | GK | | 4-0 | 21-31-11 | D41473J | 21 | | | D41713J | 9 | | | 115-199 |
| 0003 | 24 | | GK | | 5-0 | 21-33-12 | D40874J | 12 | | | TB0168Y | C011 | BJ | | 001-099 |
| 0003 | 24 | | GK | | 7-0 | 21-33-12 | D40874J | 12 | | | TB0168Y | C011 | BJ | | 115-199 |
| 0004 | 20 | | GK | | 2-0 | 21-45-11 | D40696J | 6 | | | D40582J | 1 | | | 001-099 |
| 0004 | 20 | | GK | | 6-0 | 21-45-11 | D40696J | 6 | | | D40582J | 1 | | | 115-199 |
| 0005 | 20 | | GK | | 3-0 | 21-58-11 | D40696J | 12 | | | SM00010 | | WI | | 001-099 |
| 0005 | 20 | | GK | | 4-0 | 21-58-11 | D40696J | 12 | | | SM00010 | | WI | | 115-199 |
| 0006 | 20 | | GK | | 3-0 | SPARE | D40056J | CAP | Y | | SM00010 | | WI | | 001-002 |
| 0006 | 20 | | GK | | 3-0 | 21-58-11 | D40056J | CAP | Y | | SM00010 | | WI | | 003-099 |
| 0006 | 20 | | GK | | 4-0 | 21-58-11 | D40056J | CAP | Y | | SM00010 | | WI | | 115-199 |
| 0007 | 20 | | GK | | 4-0 | 21-58-11 | D41060J | 4 | | | SM00010 | | WI | | ALL |
| 0010 | 24 | | GK | | 2-0 | 21-58-12 | D41024J | 1 | | | D40056J | 27 | | | 001-099 |
| 0010 | 24 | | GK | | 3-0 | 21-58-12 | D41024J | 1 | | | D40056J | 27 | | | 115-199 |
| 0012 | 24 | | GK | | 4-0 | 21-58-12 | SM00012 | | WI | | D40728J | 2 | | | 001-099 |
| 0012 | 24 | | GK | | 4-0 | 21-58-12 | D40728J | 2 | | | SM00012 | | WI | | 115-199 |
| 0013 | 24 | | GK | | 3-0 | 21-58-12 | SM00012 | | WI | | D40056J | 24 | | | 001-099 |
| 0013 | 24 | | GK | | 4-0 | 21-58-12 | D40056J | 24 | | | SM00012 | | WI | | 115-199 |
| 0014 | 24 | | GK | | 3-0 | 21-58-12 | D40056J | 28 | | | SM00015 | | WI | | 001-099 |
| 0014 | 24 | | GK | | 4-0 | 21-58-12 | D40056J | 28 | | | SM00015 | | WI | | 115-199 |
| 0016 | 22 | | GK | | 4-0 | 23-31-41 | D41497J | 18 | | | D40310J | 25 | | | 001-099 |
| 0016 | 22 | | GK | | 3-0 | 23-31-41 | D41497J | 18 | | | D40310J | 25 | | | 115-199 |
| 0017 | 22 | | GK | | 4-0 | 23-31-41 | D41497J | 19 | | | D40310J | 26 | | | 001-099 |
| 0017 | 22 | | GK | | 3-0 | 23-31-41 | D41497J | 19 | | | D40310J | 26 | | | 115-199 |
| 0018 | 22 | | GK | | 4-0 | 23-31-41 | D41497J | 20 | | | D40310J | 15 | | | 001-099 |
| 0018 | 22 | | GK | | 3-0 | 23-31-41 | D41497J | 20 | | | D40310J | 15 | | | 115-199 |
| 0019 | 24 | | GK | | 3-0 | 26-11-11 | D41060J | 37 | | | D41948J | 38 | | | 001-099 |
| 0019 | 24 | | GK | | 5-0 | 26-11-11 | D41060J | 37 | | | D41938J | 15 | | | 115-199 |
| 0020 | 24 | | GK | | 8-0 | 26-15-11 | D41060J | 38 | | | TB0166A | A024 | 2 | | 001-099 |
| 0020 | 24 | | GK | | 4-0 | 26-15-11 | D41060J | 38 | | | D41958J | 36 | | | 115-199 |
| 0023 | 20 | | GK | | 4-0 | 21-61-51 | D40060J | 5 | | | D40874J | 8 | | | ALL |
| 0024 | 24 | | GK | | 7-0 | 30-31-12 | TB0160Y | C007 | BJ | | D41022J | 32 | | | 115-199 |
| 0025 | 22 | | GK | | 6-0 | 27-48-21 | D00825 | 4 | | | D41493J | 19 | | | 001-099 |
| 0025 | 22 | | GK | | 5-0 | 27-48-21 | D00825 | 4 | | | D41493J | 19 | | | 115-199 |
| 0026 | 22 | | GK | | 6-0 | 27-48-21 | D00825 | 5 | | | D41493J | 20 | | | 001-099 |
| 0026 | 22 | | GK | | 5-0 | 27-48-21 | D00825 | 5 | | | D41493J | 20 | | | 115-199 |
| 0027 | 22 | | GK | | 2-0 | 27-48-21 | D00825 | 1 | | | GD01677 | AC.. | F | | ALL |
| 0028 | 22 | | GK | | 2-0 | 27-48-21 | D00825 | 6 | | | GD01678 | ST.. | F | | ALL |
| 0029 | 24 | | GK | | 3-0 | 27-58-11 | D40696J | 36 | | | D41612J | 8 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0029 | 22 | | GK | | 2-0 | 27-58-11 | D40696J | 36 | | | D41612J | 8 | | | 115-199 |
| 0030 | 22 | | GK | | 5-0 | 27-62-11 | D41022J | 7 | | | M00963 | A | C | | 001-099 |
| 0030 | 20 | | GK | | 6-0 | 27-62-11 | D41022J | 7 | | | M00963 | A | C | | 115-199 |
| 0031 | 22 | | GK | | 2-0 | 27-62-11 | M00963 | B | C | | TB0168Y | C004 | BJ | | 001-099 |
| 0031 | 20 | | GK | | 3-0 | 27-62-11 | M00963 | B | C | | TB0168Y | C004 | BJ | | 115-199 |
| 0032 | 20 | | GK | | 5-0 | 27-62-11 | D41022J | 8 | | | TB0168Y | C004 | BJ | | 001-099 |
| 0032 | 20 | | GK | | 6-0 | 27-62-11 | D41022J | 8 | | | TB0168Y | C004 | BJ | | 115-199 |
| 0033 | 18 | | GK | | 6-0 | 29-21-31 | D41958J | 53 | 18 | | SM00001 | | WI | | 115-199 |
| 0034 | 12 | | HA | | 6-0 | 29-21-31 | D42096J | 16 | | | SM00001 | | WI | | 115-199 |
| 0037 | 12 | | HA | | 7-6 | 29-21-31 | D42096J | 14 | | | SM00002 | | WI | | ALL |
| 0038 | 20 | | GK | | 4-0 | 28-22-31 | D41948J | 12 | | | D41958J | 17 | | | 001-008, 115-199 |
| 0038 | 20 | | GK | | 2-0 | 28-22-31 | D41850J | 51 | | | D41958J | 17 | | | 009-099 |
| 0039 | 24 | | GK | | 3-0 | 24-28-11 | D40542J | 11 | | | D41473J | 13 | | | 001-099 |
| 0039 | 24 | | GK | | 4-0 | 24-28-11 | D40542J | 11 | | | D41473J | 13 | | | 115-199 |
| 0040 | 24 | | GK | | 5-0 | 24-51-71 | D40874J | 15 | | | TB0168Y | C005 | BJ | | 001-099 |
| 0040 | 24 | | GK | | 7-0 | 24-51-71 | D40874J | 15 | | | TB0168Y | C019 | BJ | | 115-199 |
| 0041 | 24 | | GK | | 7-0 | 24-51-71 | D40608J | 11 | | | TB0168Y | C005 | BJ | | 001-099 |
| 0041 | 24 | | GK | | 7-0 | 24-51-71 | D40608J | 11 | | | TB0168Y | C019 | BJ | | 115-199 |
| 0042 | 24 | | GK | | 6-0 | 30-31-11 | TB0168Y | A012 | BJ | | D41020J | 4 | | | 001-099 |
| 0042 | 24 | | GK | | 7-0 | 30-31-11 | TB0168Y | A012 | BJ | | D41020J | 4 | | | 115-199 |
| 0043 | 24 | | GK | | 7-0 | 24-22-22 | TB0160Y | A002 | BJ | | D41022J | 34 | | | 001-099 |
| 0043 | 24 | | GK | | 5-0 | 24-22-22 | TB0168Y | C012 | BJ | | D41022J | 34 | | | 115-199 |
| 0044 | 24 | | GK | | 7-0 | 24-22-22 | TB0160Y | A002 | BJ | | D41713J | 3 | | | 001-099 |
| 0044 | 24 | | GK | | 7-0 | 24-22-22 | TB0168Y | C012 | BJ | | D41713J | 3 | | | 115-199 |
| 0045 | 22 | | GK | | 3-0 | 27-23-11 | D40582J | 35 | | | D40574J | 4 | | | 001-099 |
| 0045 | 22 | | GK | | 4-0 | 27-23-11 | D40582J | 35 | | | D41475J | 39 | | | 115-199 |
| 0046 | 22 | | GK | | 8-0 | 27-23-11 | D40582J | 34 | | | D00598 | D3 | | * | 001-099 |
| 0046 | 22 | | GK | | 6-0 | 27-23-11 | D40582J | 34 | | | TB0168Y | C022 | BJ | | 115-199 |
| 0047 | 22 | | GK | | 8-0 | 27-23-11 | TB0168Y | C022 | BJ | | D41475J | 41 | | | 115-199 |
| 0050 | 22 | | GK | | 3-0 | 32-44-11 | D40914J | 1 | | | D41958J | 48 | | | 001-099 |
| 0050 | 22 | | GK | | 2-0 | 32-44-11 | D40914J | 1 | | | D41958J | 48 | | | 115-199 |
| 0053 | 24 | | GK | | 4-0 | 30-31-11 | D40860J | 2 | | | D40874J | 39 | | | 115-199 |
| 0054 | 24 | | GK | | 5-0 | 30-31-11 | D40874J | 36 | | | TB0168Y | A012 | BJ | | 001-099 |
| 0054 | 24 | | GK | | 7-0 | 30-31-11 | D40874J | 36 | | | TB0168Y | A012 | BJ | | 115-199 |
| 0057 | 20 | | GK | | 3-0 | 33-23-11 | D40696J | 41 | | | D40310J | 31 | | | ALL |
| 0058 | 20 | | GK | | 3-0 | 33-23-12 | D40696J | 42 | | | D40310J | 32 | | | 001-099 |
| 0058 | 20 | | GK | | 4-0 | 33-23-12 | D40696J | 42 | | | D40310J | 32 | | | 115-199 |
| 0059 | 20 | | GK | | 3-0 | 33-23-13 | D40696J | 43 | | | D40310J | 33 | | | 001-099 |
| 0059 | 20 | | GK | | 4-0 | 33-23-13 | D40696J | 43 | | | D40310J | 33 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0060 | 20 | | GK | | 3-0 | 33-23-14 | D40696J | 44 | | | D40310J | 34 | | | 001-099 |
| 0060 | 20 | | GK | | 4-0 | 33-23-14 | D40696J | 44 | | | D40310J | 34 | | | 115-199 |
| 0061 | 22 | | GK | | 3-0 | 33-24-11 | D40716J | 9 | | | D40310J | 7 | | | ALL |
| 0062 | 16 | | GK | | 3-0 | 33-24-11 | D40716J | 7 | 16 | | D40310J | 1 | | | ALL |
| 0063 | 22 | | GK | | 4-0 | 33-25-11 | D41497J | 13 | | | D40310J | 2 | | | 001-099 |
| 0064 | 22 | | GK | | 4-0 | 33-25-11 | D40696J | 20 | | | SM00003 | | WI | | 001-099 |
| 0064 | 22 | | GK | | 6-0 | 33-25-11 | D40696J | 20 | | | TB0168Y | A013 | BJ | | 115-199 |
| 0065 | 22 | | GK | | 1-0 | 33-25-11 | D40310J | 5 | | | SM00003 | | WI | | 001-099 |
| 0065 | 22 | | GK | | 6-0 | 33-25-11 | D40310J | 5 | | | TB0168Y | A013 | BJ | | 115-199 |
| 0066 | 22 | | GK | | 1-0 | 33-25-13 | D40310J | 35 | | | SM00003 | | WI | | 001-099 |
| 0066 | 22 | | GK | | 6-0 | 33-25-13 | D40310J | 35 | | | TB0168Y | A013 | BJ | | 115-199 |
| 0067 | 20 | | GK | | 3-0 | 33-31-11 | D40716J | 15 | | | D40390J | 2 | | | 001-099 |
| 0067 | 20 | | GK | | 4-0 | 33-31-11 | D40716J | 15 | | | D40390J | 2 | | | 115-199 |
| 0069 | 20 | | GK | | 4-0 | 33-41-11 | D40608J | 35 | | | D41612J | 20 | | | ALL |
| 0070 | 20 | | GK | | 3-0 | 33-42-11 | D40582J | 32 | | | D40390J | 3 | | | 001-099 |
| 0070 | 20 | | GK | | 4-0 | 33-42-11 | D40582J | 32 | | | D40390J | 3 | | | 115-199 |
| 0071 | 18 | | GK | | 3-0 | 33-42-21 | D40910J | 8 | | | D40390J | 1 | | | ALL |
| 0072 | 24 | | GK | | 9-0 | 21-25-11 | D05192 | 2 | | | D41020J | 21 | | | 001-099 |
| 0072 | 24 | | GK | | 8-0 | 21-25-11 | D05192 | 2 | | | D41020J | 21 | | | 115-199 |
| 0074 | 24 | | GK | | 6-0 | 34-12-11 | TB0168Y | A005 | BJ | | T00139 | HV | D | | 001-099 |
| 0074 | 24 | | GK | | 5-0 | 34-12-11 | TB0168Y | A016 | BJ | | T00139 | HV | D | | 115-199 |
| 0075 | 20 | | GK | | 7-0 | 34-12-11 | D41473J | 39 | | | T00139 | LV | D | | 001-099 |
| 0075 | 20 | | GK | | 6-0 | 34-12-11 | D41473J | 39 | | | T00139 | LV | D | | 115-199 |
| 0076 | 20 | | GK | | 7-0 | 34-12-11 | D41473J | 40 | | | T00139 | G | D | | 001-099 |
| 0076 | 20 | | GK | | 6-0 | 34-12-11 | D41473J | 40 | | | T00139 | G | D | | 115-199 |
| 0077 | 16 | | GK | | 4-0 | 35-21-12 | D40310J | 39 | | | D41024J | 21 | | | ALL |
| 0078 | 16 | | GK | | 4-0 | 35-21-13 | D40310J | 29 | | | D41024J | 23 | | | ALL |
| 0079 | 24 | | GK | | 7-0 | 36-11-11 | D40874J | 30 | | | TB0168Y | A014 | BJ | | 115-199 |
| 0080 | 24 | | GK | | 7-0 | 36-11-11 | D41475J | 4 | | | TB0168Y | A014 | BJ | | 115-199 |
| 0081 | 20 | | GK | | 7-0 | 36-11-11 | D40060J | 13 | | | D05258 | X2 | | | ALL |
| 0082 | 24 | | GK | | 6-0 | 36-11-11 | D40060J | 45 | | | TB0168Y | A014 | BJ | | 115-199 |
| 0083 | 24 | | GK | | 4-0 | 36-11-12 | D40060J | 1 | | | D40696J | 1 | | | 001-099 |
| 0083 | 24 | | GK | | 5-0 | 36-11-12 | D40060J | 1 | | | D40696J | 1 | | | 115-199 |
| 0085 | 24 | | GK | | 6-0 | 36-11-41 | D41022J | 33 | | | TB0168Y | C013 | BJ | | 115-199 |
| 0086 | 24 | | GK | | 6-0 | 36-11-41 | D05258 | B3 | | * | D41022J | 33 | | | 001-009 |
| 0086 | 24 | | GK | | 5-0 | 36-11-41 | D07036 | A2 | | * | D41022J | 33 | | | 010-099 |
| 0086 | 24 | | GK | | 4-0 | 36-11-41 | D05258 | B3 | | | TB0168Y | C013 | BJ | | 115-199 |
| 0087 | 24 | | GK | | 4-0 | 36-21-11 | D40696J | 13 | | | D40060J | 7 | | | ALL |
| 0088 | 22 | | GK | | 9-0 | 30-32-11 | D40910J | 21 | | | D00592 | C3 | | * | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0088 | 22 | | GK | | 8-0 | 30-32-11 | D40910J | 21 | | | TB0165Y | A011 | BJ | | 115-199 |
| 0091 | 22 | | GK | | 6-0 | 78-34-11 | D41948J | 32 | | | TB0168Y | A015 | BJ | | 115-199 |
| 0092 | 22 | | GK | | 6-0 | 78-34-11 | TB0168Y | C014 | BJ | | D41462J | 31 | | | 115-199 |
| 0093 | 24 | | GK | | 7-0 | 80-11-11 | D41958J | 16 | | | TB0168A | A008 | 2 | | 001-099 |
| 0093 | 24 | | GK | | 5-0 | 80-11-11 | D41958J | 16 | | | TB0168A | A008 | 2 | | 115-199 |
| 0095 | 24 | | GK | | 3-0 | 80-11-11 | M10334 | A | C | | TB0168A | C008 | 2 | | ALL |
| 0096 | 24 | | GK | | 2-0 | 80-11-11 | M10334 | B | C | | TB0168Y | A004 | BJ | | 001-099 |
| 0096 | 24 | | GK | | 3-0 | 80-11-11 | M10334 | B | C | | TB0168Y | C015 | BJ | | 115-199 |
| 0097 | 24 | | GK | | 6-0 | 80-11-11 | D41938J | 8 | | | TB0168Y | A004 | BJ | | 001-099 |
| 0097 | 24 | | GK | | 6-0 | 80-11-11 | D41938J | 8 | | | TB0168Y | C015 | BJ | | 115-199 |
| 0099 | 20 | | GK | | 3-0 | 28-22-31 | D41850J | 1 | | | D41958J | 19 | | | 001-008, 115-199 |
| 0099 | 20 | | GK | | 2-0 | 28-22-31 | D41850J | 1 | | | D41958J | 19 | | | 009-099 |
| 0100 | 20 | | GK | | 3-0 | 28-22-31 | D41850J | 2 | | | D41958J | 18 | | | 001-008, 115-199 |
| 0100 | 20 | | GK | | 2-0 | 28-22-31 | D41850J | 2 | | | D41958J | 18 | | | 009-099 |
| 0101 | 20 | | GK | | 5-0 | 32-35-11 | K10369 | X1 | C | | TB0168Y | A020 | BJ | | 115-199 |
| 0102 | 24 | | GK | | 5-0 | 34-12-11 | D40728J | 25 | | | TB0168Y | A005 | BJ | | 001-099 |
| 0102 | 24 | | GK | | 6-0 | 34-12-11 | D40728J | 25 | | | TB0168Y | A016 | BJ | | 115-199 |
| 0103 | 24 | | GK | | 6-0 | 34-12-11 | D41497J | 37 | | | TB0168Y | A005 | BJ | | 001-099 |
| 0103 | 24 | | GK | | 7-0 | 34-12-11 | D41497J | 37 | | | TB0168Y | A016 | BJ | | 115-199 |
| 0104 | 24 | | GK | | 6-0 | 21-33-12 | D41475J | 43 | | | TB0168Y | C011 | BJ | | 001-099 |
| 0104 | 24 | | GK | | 7-0 | 21-33-12 | D41475J | 43 | | | TB0168Y | C011 | BJ | | 115-199 |
| 0107 | 20 | | GK | | 2-0 | 32-35-11 | K10369 | X2 | C | | GD01679 | DC.. | F | | ALL |
| 0108 | 12 | | HA | | 1-0 | 32-35-11 | K10369 | A2 | E | | K10369 | A3 | E | | ALL |
| 0109 | 12 | | HA | | 1-1 | 32-35-11 | K10369 | A4 | E | | GD01679 | DC.. | F | | 001-099 |
| 0109 | 12 | | HA | | 1-6 | 32-35-11 | K10369 | A4 | E | | GD01679 | DC.. | F | | 115-199 |
| 0110 | 24 | | GK | | 2-0 | 34-12-12 | D41473J | 41 | | | D40582J | 10 | | | 001-099 |
| 0110 | 24 | | GK | | 5-0 | 34-12-12 | D41473J | 41 | | | D40582J | 10 | | | 115-199 |
| 0111 | 20 | | GK | | 4-0 | 27-62-11 | D41612J | 1 | | | D41020J | 5 | | | 001-099 |
| 0111 | 20 | | GK | | 5-0 | 27-62-11 | D41612J | 1 | | | D41020J | 5 | | | 115-199 |
| 0112 | 24 | | GK | | 8-0 | 21-51-12 | D40874J | 17 | | | D02948 | X1 | | * | 001-099 |
| 0112 | 24 | | GK | | 5-0 | 21-51-12 | D40874J | 17 | | | D40060J | 49 | | | 115-199 |
| 0113 | 20 | | GK | | 4-0 | 21-51-12 | D40696J | 16 | | | D40060J | 25 | | | ALL |
| 0114 | 20 | | GK | | 4-0 | 28-22-31 | D41948J | 15 | | | D41958J | 23 | | | 001-008, 115-199 |
| 0115 | 22 | | GK | | 4-0 | 32-42-11 | D40582J | 48 | | | D41544J | 26 | | | 001-099 |
| 0115 | 22 | | GK | | 4-0 | 32-42-11 | D40696J | 26 | | | D41544J | 26 | | | 115-199 |
| 0116 | 22 | | GK | | 8-0 | 29-11-22 | D41020J | 32 | | | D03076 | X1 | | * | 001-099 |
| 0116 | 22 | | GK | | 7-0 | 29-11-22 | D41020J | 32 | | | TB0168Y | A011 | BJ | | 115-199 |
| 0119 | 20 | | GK | | 3-0 | 29-11-22 | TB0168X | B017 | BJ | | M00500 | A | C | | 115-199 |
| 0120 | 20 | | GK | | 2-0 | 29-11-22 | GD01690 | DC.. | 2 | | M00500 | B | C | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0120 | 20 | | GK | | 3-0 | 29-11-22 | GD01690 | DC.. | 2 | | M00500 | B | C | | 115-199 |
| 0121 | 20 | | GK | | 3-0 | 29-11-31 | TB0168X | C017 | BJ | | M10020 | A | C | | 115-199 |
| 0122 | 20 | | GK | | 3-0 | 29-11-31 | GD01690 | DC.. | 2 | | M10020 | B | C | | ALL |
| 0123 | 24 | | GK | | 2-0 | 21-33-12 | D03230 | | 4 | | GD01690 | ST.. | 2 | | ALL |
| 0124 | 24 | | GK | | 4-0 | 36-11-12 | D40874J | | 33 | | D40060J | 31 | | | 001-099 |
| 0124 | 24 | | GK | | 6-0 | 36-11-12 | D40874J | | 33 | | D40060J | 31 | | | 115-199 |
| 0125 | 22 | | GK | | 8-0 | 29-11-22 | D41020J | | 31 | | TB0166G | 25 | 2 | | 001-099 |
| 0125 | 22 | | GK | | 6-0 | 29-11-22 | D41020J | | 31 | | TB0165G | 16 | 2 | | 115-199 |
| 0126 | 20 | | GK | | 8-0 | 36-11-11 | TB0163X | A001 | BJ | | TB0166Z | 16 | BJ | | 115-199 |
| 0127 | 20 | | GK | | 8-0 | 36-11-11 | D05258 | X1 | | | TB0166Z | 12 | BJ | | 001-009 |
| 0127 | 20 | | GK | | 10-0 | 36-11-11 | D05258 | X1 | | | TB0166Z | 12 | BJ | | 010-099 |
| 0127 | 20 | | GK | | 3-0 | 36-11-11 | D05258 | X1 | | | TB0163X | A001 | BJ | | 115-199 |
| 0128 | 24 | | GK | | 2-0 | 36-11-41 | D05258 | B2 | | | GD01693 | DC.. | 2 | | ALL |
| 0129 | 24 | | GK | | 2-0 | 36-11-11 | D05258 | A2 | | | GD01693 | DC.. | 2 | | ALL |
| 0130 | 24 | | GK | | 8-0 | 36-11-11 | D05258 | A1 | | | D40060J | 45 | | | 001-099 |
| 0130 | 24 | | GK | | 4-0 | 36-11-11 | D05258 | A1 | | | TB0168Y | A014 | BJ | | 115-199 |
| 0131 | 24 | | GK | | 2-0 | 21-33-12 | D03230 | | 2 | | GD01690 | DC.. | 2 | | ALL |
| 0132 | 24 | | GK | | 3-0 | 21-33-12 | D03230 | | 1 | | TB0168Y | C011 | BJ | | ALL |
| 0133 | 24 | | GK | | 6-0 | 31-51-31 | D41497J | | 9 | | TB0168Y | C011 | BJ | | 001-099 |
| 0133 | 24 | | GK | | 7-0 | 31-51-31 | D41497J | | 9 | | TB0168Y | C011 | BJ | | 115-199 |
| 0151 | 24 | | GK | | 5-0 | 29-33-11 | D40874J | | 7 | | TB0168A | A013 | 2 | | 001-099 |
| 0151 | 24 | | GK | | 8-0 | 29-33-11 | D40874J | | 7 | | TB0362C | A001 | 2 | | 115-199 |
| 0152 | 24 | | GK | | 7-0 | 29-33-11 | D41850J | | 17 | | TB0168A | A009 | 2 | | 001-099 |
| 0152 | 24 | | GK | | 9-0 | 29-33-11 | D41850J | | 17 | | TB0362C | A002 | 2 | | 115-199 |
| 0153 | 24 | | GK | | 7-0 | 29-33-11 | D40608J | | 3 | | TB0168A | A010 | 2 | | 001-099 |
| 0153 | 24 | | GK | | 9-0 | 29-33-11 | D40608J | | 3 | | TB0362C | A003 | 2 | | 115-199 |
| 0154 | 22 | | GK | | 4-0 | 38-13-11 | D40728J | | 11 | | D41022J | 27 | | | 001-099 |
| 0154 | 22 | | GK | | 5-0 | 38-13-11 | D40728J | | 11 | | D41022J | 27 | | | 115-199 |
| 0155 | 22 | | GK | | 4-0 | 38-13-11 | D40728J | | 5 | | D41022J | 26 | | | 001-099 |
| 0155 | 22 | | GK | | 5-0 | 38-13-11 | D40728J | | 5 | | D41022J | 26 | | | 115-199 |
| 0156 | 24 | | GK | | 4-0 | 21-61-51 | D40696J | | 25 | | D41544J | 55 | | | ALL |
| 0167 | 24 | | GK | | 5-0 | 29-33-11 | D40874J | | 28 | | TB0168A | C013 | 2 | | 001-099 |
| 0167 | 24 | | GK | | 8-0 | 29-33-11 | D40874J | | 28 | | TB0362C | C001 | 2 | | 115-199 |
| 0170 | 24 | | GK | | 8-0 | 23-12-11 | D04510 | | 11 | | D41475J | 22 | | | ALL |
| 0171 | 24 | | GK | | 2-0 | 23-12-11 | D04510 | | 10 | | GD01670 | DC.. | 2 | | 001-099 |
| 0171 | 24 | | GK | | 3-0 | 23-12-11 | D04510 | | 10 | | GD01670 | DC.. | 2 | | 115-199 |
| 0173 | 20 | | GK | | 5-0 | 80-11-11 | D41958J | | 40 | | D41938J | 4 | | | 001-099 |
| 0174 | 24 | | GK | | 5-0 | 29-33-11 | D41020J | | 50 | | TB0168A | A013 | 2 | | 001-099 |
| 0174 | 24 | | GK | | 8-0 | 29-33-11 | D41020J | | 50 | | TB0362C | A001 | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 0178 | 24 | GK | | | 7-0 | 29-33-11 | D41850J | | 4 | | TB0168A | C009 | 2 | | 001-099 |
| 0178 | 24 | GK | | | 9-0 | 29-33-11 | D41850J | | 4 | | TB0362C | C002 | 2 | | 115-199 |
| 0194 | 24 | GK | | | 7-0 | 29-33-11 | D41850J | | 5 | | TB0168A | A009 | 2 | | 001-099 |
| 0194 | 24 | GK | | | 9-0 | 29-33-11 | D41850J | | 5 | | TB0362C | A002 | 2 | | 115-199 |
| 0198 | 24 | GK | | | 7-0 | 29-33-11 | D40608J | | 2 | | TB0168A | C010 | 2 | | 001-099 |
| 0198 | 24 | GK | | | 9-0 | 29-33-11 | D40608J | | 2 | | TB0362C | C003 | 2 | | 115-199 |
| 0204 | 24 | GK | | | 1-0 | 21-58-11 | TB0161A | A010 | 2 | | TB0161A | A011 | 2 | | 001-099 |
| 0204 | 24 | GK | | | 3-0 | 21-58-11 | TB0161A | A010 | 2 | | TB0161A | A011 | 2 | | 115-199 |
| 0207 | 24 | GK | | | 3-0 | 21-58-11 | D40056J | CAP | Y | | SM00015 | | WI | | 001-099 |
| 0207 | 24 | GK | | | 4-0 | 21-58-11 | SM00037 | | WI | | SM00015 | | WI | | 115-199 |
| 0209 | 24 | GK | | | 7-0 | 21-58-11 | D40874J | | 34 | | SM00037 | | WI | | 115-199 |
| 0210 | 24 | GK | | | 7-0 | 21-58-11 | D40874J | | 34 | | TB0161A | C002 | 2 | | 001-099 |
| 0210 | 24 | GK | | | 7-0 | 21-58-11 | D40874J | CAP | Y | | TB0161A | C010 | 2 | | 115-199 |
| 0211 | 16 | GK | | | 3-0 | 29-11-22 | D03076 | | A2 | | TB0166G | 25 | 2 | | 001-099 |
| 0211 | 16 | GK | | | 4-0 | 29-11-22 | D03076 | | A2 | | TB0165G | 16 | 2 | | 115-199 |
| 0213 | 22 | GK | | | 10-0 | 33-16-11 | D02596 | | B1 | | D40874J | 11 | | | 001-099 |
| 0213 | 22 | GK | | | 8-0 | 33-16-11 | D02596 | | B1 | | D40874J | 11 | | | 115-199 |
| 0215 | 24 | GK | | | 4-0 | 21-58-11 | D41544J | | 24 | | SM00015 | | WI | | 115-199 |
| 0218 | 24 | GK | | | 3-0 | 21-58-11 | D41060J | | 1 | | SM00015 | | WI | | 001-099 |
| 0218 | 24 | GK | | | 4-0 | 21-58-11 | D41060J | | 1 | | SM00015 | | WI | | 115-199 |
| 0220 | 24 | GK | | | 7-0 | 27-58-11 | D40696J | | 35 | | TB0165Y | A009 | BJ | | 001-099 |
| 0220 | 22 | GK | | | 6-0 | 27-51-51 | D40696J | | 34 | | TB0166Y | A001 | BJ | | 115-199 |
| 0221 | 22 | GK | | | 7-0 | 27-51-51 | D03022 | | A2 | * | D40696J | 34 | | | 001-099 |
| 0221 | 22 | GK | | | 4-0 | 27-51-51 | D03022 | | A2 | | TB0166Y | A001 | BJ | | 115-199 |
| 0222 | 22 | GK | | | 1-0 | 27-51-51 | D03022 | | X1 | | D03022 | A2 | | * | 001-099 |
| 0222 | 22 | GK | | | 4-0 | 27-51-51 | D03022 | | X1 | | TB0166Y | A001 | BJ | | 115-199 |
| 0223 | 22 | GK | | | 7-0 | 27-51-51 | D03022 | | X2 | | D41612J | 46 | | | 001-099 |
| 0223 | 22 | GK | | | 8-0 | 27-51-51 | D03022 | | X2 | | D41612J | 46 | | | 115-199 |
| 0224 | 22 | GK | | | 7-0 | 27-51-51 | D03022 | | A1 | | D41612J | 23 | | | 001-099 |
| 0224 | 20 | GK | | | 8-0 | 27-51-51 | D03022 | | A1 | | D41612J | 23 | | | 115-199 |
| 0225 | 22 | GK | | | 6-0 | 27-58-11 | D40696J | | 35 | | TB0166Y | C001 | BJ | | 115-199 |
| 0226 | 24 | GK | | | 3-0 | 27-58-11 | D02958 | | 4 | | TB0165Y | C008 | BJ | | 001-099 |
| 0226 | 22 | GK | | | 4-0 | 27-58-11 | D02958 | | 4 | | TB0166Y | C004 | BJ | | 115-199 |
| 0227 | 24 | GK | | | 3-0 | 27-58-11 | D02958 | | 10 | | TB0165Y | C008 | BJ | | 001-099 |
| 0227 | 22 | GK | | | 4-0 | 27-58-11 | D02958 | | 10 | | TB0166Y | C004 | BJ | | 115-199 |
| 0228 | 24 | GK | | | 3-0 | 27-58-11 | D02958 | | 8 | | TB0165Y | A008 | BJ | | 001-099 |
| 0228 | 22 | GK | | | 4-0 | 27-58-11 | D02958 | | 8 | | TB0166Y | A004 | BJ | | 115-199 |
| 0229 | 24 | GK | | | 3-0 | 27-58-11 | D02958 | | 2 | | TB0165Y | A008 | BJ | | 001-099 |
| 0229 | 22 | GK | | | 4-0 | 27-58-11 | D02958 | | 2 | | TB0166Y | A004 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0230 | 22 | | GA | | 8-0 | 27-58-11 | D41612J | | | 7 | TB0166Y | A002 | BJ | | 010-099 |
| 0230 | 22 | | GK | | 8-0 | 27-58-11 | D41612J | | | 7 | TB0166Y | A002 | BJ | | 115-199 |
| 0231 | 24 | | GK | | 8-0 | 27-58-11 | D02958 | | | 3 | D41612J | | 7 | | 001-009 |
| 0231 | 24 | | GK | | 8-0 | 27-58-11 | D02958 | | | 3 | TB0166Y | A002 | BJ | | 010-099 |
| 0231 | 22 | | GK | | 4-0 | 27-58-11 | D02958 | | | 3 | TB0166Y | A002 | BJ | | 115-199 |
| 0232 | 22 | | GA | | 8-0 | 27-58-11 | D41612J | | | 6 | TB0166Y | C002 | BJ | | 010-099 |
| 0232 | 22 | | GK | | 8-0 | 27-58-11 | D41612J | | | 6 | TB0166Y | C002 | BJ | | 115-199 |
| 0233 | 24 | | GK | | 8-0 | 27-58-11 | D02958 | | | 13 | D41612J | | 6 | | 001-009 |
| 0233 | 24 | | GK | | 8-0 | 27-58-11 | D02958 | | | 13 | TB0166Y | C002 | BJ | | 010-099 |
| 0233 | 22 | | GK | | 4-0 | 27-58-11 | D02958 | | | 13 | TB0166Y | C002 | BJ | | 115-199 |
| 0234 | 24 | | GK | | 8-0 | 27-58-11 | D41690J | | | 8 | TB0165Y | A009 | BJ | | 001-099 |
| 0234 | 22 | | GK | | 7-0 | 27-58-11 | D41690J | | | 8 | TB0166Y | C001 | BJ | | 115-199 |
| 0235 | 22 | | GK | | 7-0 | 27-58-11 | D41690J | | | 7 | TB0166Y | A003 | BJ | | 115-199 |
| 0236 | 24 | | GK | | 8-0 | 27-58-11 | D02958 | | | 9 | D41690J | | 7 | | 001-099 |
| 0236 | 22 | | GK | | 4-0 | 27-58-11 | D02958 | | | 9 | TB0166Y | A003 | BJ | | 115-199 |
| 0237 | 22 | | GK | | 7-0 | 27-58-11 | D41690J | | | 6 | TB0166Y | C003 | BJ | | 115-199 |
| 0238 | 24 | | GK | | 8-0 | 27-58-11 | D02958 | | | 14 | D41690J | | 6 | | 001-099 |
| 0238 | 22 | | GK | | 4-0 | 27-58-11 | D02958 | | | 14 | TB0166Y | C003 | BJ | | 115-199 |
| 0239 | 24 | | GK | | 7-0 | 27-58-11 | D41473J | | | 34 | D02958 | | 11 | | 001-099 |
| 0239 | 22 | | GK | | 8-0 | 27-58-11 | D41473J | | | 34 | D02958 | | 11 | | 115-199 |
| 0240 | 24 | | GK | | 7-0 | 27-58-11 | D41473J | | | 35 | D02958 | | 7 | | 001-099 |
| 0240 | 22 | | GK | | 8-0 | 27-58-11 | D41473J | | | 35 | D02958 | | 7 | | 115-199 |
| 0241 | 24 | | GK | | 7-0 | 27-58-11 | D41473J | | | 36 | D02958 | | 5 | | 001-099 |
| 0241 | 22 | | GK | | 8-0 | 27-58-11 | D41473J | | | 36 | D02958 | | 5 | | 115-199 |
| 0242 | 24 | | GK | | 7-0 | 27-58-11 | D41473J | | | 37 | D02958 | | 1 | | 001-099 |
| 0242 | 22 | | GK | | 8-0 | 27-58-11 | D41473J | | | 37 | D02958 | | 1 | | 115-199 |
| 0243 | 24 | | GK | | 7-0 | 27-58-11 | D40582J | | | 24 | D02958 | | 6 | | 001-099 |
| 0243 | 24 | | GK | | 8-0 | 27-58-11 | D40582J | | | 24 | D02958 | | 6 | | 115-199 |
| 0244 | 24 | | GK | | 7-0 | 27-58-11 | D41612J | | | 30 | D02958 | | 12 | | 001-099 |
| 0244 | 24 | | GK | | 8-0 | 27-58-11 | D41612J | | | 30 | D02958 | | 12 | | 115-199 |
| 0253 | 20 | | GK | | 7-0 | 27-62-11 | D03200 | | | A2 | D41713J | | 6 | | ALL |
| 0254 | 20 | | GK | | 3-0 | 27-62-11 | D03200 | | | A3 | GD01685 | DC.. | 2 | | 001-099 |
| 0254 | 20 | | GK | | 4-0 | 27-62-11 | D03200 | | | A3 | GD01683 | DC.. | 2 | | 115-199 |
| 0255 | 20 | | GK | | 3-0 | 27-62-11 | D03200 | | | A1 | TB0166Z | | 22 | BJ | 001-099 |
| 0255 | 20 | | GK | | 8-0 | 27-62-11 | D03200 | | | A1 | TB0165Z | | 6 | BJ | 115-199 |
| 0256 | 20 | | GK | | 3-0 | 27-62-11 | D03200 | | | B2 | TB0166Z | | 22 | BJ | 001-099 |
| 0256 | 20 | | GK | | 4-0 | 27-62-11 | D03200 | | | B2 | TB0165Z | | 6 | BJ | 115-199 |
| 0257 | 20 | | GK | | 3-0 | 27-62-11 | D03198 | | | A1 | TB0166Z | | 22 | BJ | 001-099 |
| 0257 | 20 | | GK | | 8-0 | 27-62-11 | D03198 | | | A1 | TB0165Z | | 6 | BJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 0258 | 20 | GK | | | 7-0 | 27-62-11 | D40696J | 28 | | | TB0166Z | 22 | BJ | | 001-099 |
| 0258 | 20 | GK | | | 7-0 | 27-62-11 | D40696J | 28 | | | TB0165Z | 6 | BJ | | 115-199 |
| 0259 | 20 | GK | | | 2-0 | 27-62-11 | D03196 | D2 | | | TB0166Z | 22 | BJ | | 001-099 |
| 0259 | 20 | GK | | | 4-0 | 27-62-11 | D03196 | D2 | | | TB0165Z | 6 | BJ | | 115-199 |
| 0260 | 20 | GK | | | 2-0 | 27-62-11 | D03194 | D2 | | | TB0166Z | 22 | BJ | | 001-099 |
| 0260 | 20 | GK | | | 4-0 | 27-62-11 | D03194 | D2 | | | TB0165Z | 6 | BJ | | 115-199 |
| 0261 | 20 | GK | | | 8-0 | 27-62-11 | D41020J | 15 | | | TB0166Z | 22 | BJ | | 001-099 |
| 0261 | 20 | GK | | | 7-0 | 27-62-11 | D41020J | 15 | | | TB0165Z | 6 | BJ | | 115-199 |
| 0262 | 20 | GK | | | 1-0 | 27-62-11 | D03200 | B3 | | | D03198 | B1 | | | ALL |
| 0263 | 20 | GK | | | 1-0 | 27-62-11 | D03200 | B1 | | | D03198 | B3 | | | ALL |
| 0264 | 20 | GK | | | 4-0 | 27-62-11 | D03200 | X2 | | | GD01685 | DC.. | 2 | | 001-099 |
| 0264 | 20 | GK | | | 4-0 | 27-62-11 | D03200 | X2 | | | GD01683 | DC.. | 2 | | 115-199 |
| 0265 | 20 | GK | | | 4-0 | 27-62-11 | D03198 | A3 | | | GD01685 | DC.. | 2 | | 001-099 |
| 0265 | 20 | GK | | | 4-0 | 27-62-11 | D03198 | A3 | | | GD01683 | DC.. | 2 | | 115-199 |
| 0266 | 20 | GK | | | 4-0 | 27-62-11 | D03198 | X2 | | | GD01685 | DC.. | 2 | | 001-099 |
| 0266 | 20 | GK | | | 4-0 | 27-62-11 | D03198 | X2 | | | GD01683 | DC.. | 2 | | 115-199 |
| 0267 | 20 | GK | | | 1-0 | 27-62-11 | D03194 | C3 | | | D03194 | B3 | | | ALL |
| 0268 | 20 | GK | | | 4-0 | 27-62-11 | D03194 | B1 | | | D03198 | X1 | | | 001-009, 115-199 |
| 0268 | 20 | GK | | | 4-0 | 27-62-11 | D03194 | B1 | * | | D03198 | X1 | | | 010-099 |
| 0269 | 20 | GK | | | 3-0 | 27-62-11 | D03200 | X1 | | | D03196 | D3 | | * | 001-099 |
| 0269 | 20 | GK | | | 4-0 | 27-62-11 | D03200 | X1 | | | TB0166Y | A005 | BJ | | 115-199 |
| 0270 | 20 | GK | | | 6-0 | 27-62-11 | D03194 | D3 | * | | D41713J | 4 | | | 001-099 |
| 0270 | 20 | GK | | | 3-0 | 27-62-11 | D03194 | D3 | | | TB0166Y | A005 | BJ | | 115-199 |
| 0271 | 20 | GK | | | 1-0 | 27-62-11 | D03196 | D3 | * | | D03194 | D3 | | * | 001-099 |
| 0271 | 20 | GK | | | 3-0 | 27-62-11 | D03196 | D3 | | | TB0166Y | A005 | BJ | | 115-199 |
| 0272 | 20 | GK | | | 8-0 | 27-62-11 | D41713J | 4 | | | TB0166Y | A005 | BJ | | 115-199 |
| 0273 | 20 | GK | | | 8-0 | 27-62-11 | D41713J | 5 | | | TB0166Y | C005 | BJ | | 115-199 |
| 0274 | 20 | GK | | | 6-0 | 27-62-11 | D03194 | X1 | * | | D41713J | 5 | | | 001-099 |
| 0274 | 20 | GK | | | 3-0 | 27-62-11 | D03194 | X1 | | | TB0166Y | C005 | BJ | | 115-199 |
| 0275 | 20 | GK | | | 1-0 | 27-62-11 | D03196 | B1 | * | | D03194 | X1 | | * | 001-099 |
| 0275 | 20 | GK | | | 4-0 | 27-62-11 | D03196 | B1 | | | TB0166Y | C005 | BJ | | 115-199 |
| 0276 | 20 | GK | | | 1-0 | 27-62-11 | D03196 | X1 | | | D03196 | B1 | | * | 001-099 |
| 0276 | 20 | GK | | | 3-0 | 27-62-11 | D03196 | X1 | | | TB0166Y | C005 | BJ | | 115-199 |
| 0277 | 20 | GK | | | 1-0 | 27-62-11 | D03196 | C3 | | | D03196 | B3 | | | ALL |
| 0278 | 20 | GK | | | 3-0 | 27-62-11 | D03196 | C2 | | | GD01686 | DC.. | 2 | | 001-099 |
| 0278 | 20 | GK | | | 4-0 | 27-62-11 | D03196 | C2 | | | GD01686 | DC.. | 2 | | 115-199 |
| 0279 | 20 | GK | | | 3-0 | 27-62-11 | D03196 | A2 | | | GD01686 | DC.. | 2 | | 001-099 |
| 0279 | 20 | GK | | | 4-0 | 27-62-11 | D03196 | A2 | | | GD01686 | DC.. | 2 | | 115-199 |
| 0280 | 20 | GK | | | 6-0 | 27-62-11 | D03196 | X2 | | | D41022J | 51 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0280 | 20 | | GK | | 9-0 | 27-62-11 | D03196 | | X2 | | D41020J | 13 | | | 115-199 |
| 0281 | 20 | | GK | | 7-0 | 27-62-11 | D41713J | | 7 | | D03198 | A2 | | | 001-099 |
| 0281 | 20 | | GK | | 9-0 | 27-62-11 | D41713J | | 7 | | D03198 | A2 | | | 115-199 |
| 0282 | 20 | | GK | | 6-0 | 27-62-11 | D41022J | | 52 | | D03196 | A1 | | | 001-099 |
| 0282 | 20 | | GK | | 9-0 | 27-62-11 | D41020J | | 14 | | D03196 | A1 | | | 115-199 |
| 0283 | 20 | | GK | | 7-0 | 27-62-11 | D41020J | | 16 | | TB0168Y | A004 | BJ | | 115-199 |
| 0284 | 20 | | GK | | 7-0 | 27-62-11 | D03194 | | A1 | * | D41020J | 16 | | | 001-099 |
| 0284 | 20 | | GK | | 9-0 | 27-62-11 | D03194 | | A1 | | TB0168Y | A004 | BJ | | 115-199 |
| 0285 | 20 | | GK | | 10-0 | 27-62-11 | D03194 | | X2 | | D01782 | 4 | | | 001-099 |
| 0285 | 20 | | GK | | 9-0 | 27-62-11 | D03194 | | X2 | | TB0168X | D009 | BJ | | 115-199 |
| 0286 | 20 | | GK | | 2-0 | 27-62-11 | D03194 | | C2 | | D03202 | 3 | | | 001-099 |
| 0286 | 20 | | GK | | 4-0 | 27-62-11 | D03194 | | C2 | | D03202 | 3 | | | 115-199 |
| 0287 | 20 | | GK | | 1-0 | 27-62-11 | D03194 | | C1 | | D03196 | C1 | | | ALL |
| 0288 | 20 | | GK | | 1-0 | 27-62-11 | D03194 | | B2 | | D03196 | B2 | | | ALL |
| 0289 | 20 | | GK | | 3-0 | 27-62-11 | D03194 | | A2 | | GD01686 | DC.. | 2 | | 001-099 |
| 0289 | 20 | | GK | | 4-0 | 27-62-11 | D03194 | | A2 | | GD01686 | DC.. | 2 | | 115-199 |
| 0290 | 22 | | GK | | 9-0 | 27-62-11 | D03202 | | 4 | | TB0168Y | C004 | BJ | | 001-099 |
| 0290 | 20 | | GK | | 8-0 | 27-62-11 | D03202 | | 4 | | TB0168Y | C004 | BJ | | 115-199 |
| 0291 | 20 | | GK | | 2-0 | 27-62-11 | D03202 | | 2 | | GD01683 | DC.. | 2 | | 001-099 |
| 0291 | 20 | | GK | | 4-0 | 27-62-11 | D03202 | | 2 | | GD01683 | DC.. | 2 | | 115-199 |
| 0292 | 20 | | GK | | 3-0 | 27-62-11 | D03202 | | 7 | | D03198 | B2 | | | 001-099 |
| 0292 | 20 | | GK | | 4-0 | 27-62-11 | D03202 | | 7 | | D03198 | B2 | | | 115-199 |
| 0293 | 24 | | GK | | 7-0 | 21-58-11 | D40874J | | 35 | | TB0161A | C011 | 2 | | 001-099 |
| 0293 | 24 | | GK | | 9-0 | 21-58-11 | D40874J | | 35 | | TB0161A | C011 | 2 | | 115-199 |
| 0298 | 24 | | GK | | 4-0 | 21-58-11 | D01570 | | 6 | | D01572 | 3 | | | 001-099 |
| 0298 | 24 | | GK | | 3-0 | 21-58-11 | D01570 | | 6 | | D01572 | 3 | | | 115-199 |
| 0301 | 20 | | GK | | 8-0 | 36-11-11 | D40874J | | 31 | | TB0166Y | A010 | BJ | | 115-199 |
| 0302 | 20 | | GK | | 4-0 | 36-11-11 | D02532 | | B3 | | D02528 | X1 | | * | 001-099 |
| 0302 | 20 | | GK | | 4-0 | 36-11-11 | D02532 | | B3 | | TB0166Z | 17 | BJ | | 115-199 |
| 0303 | 20 | | GK | | 4-0 | 36-11-11 | D02532 | | A1 | | D05142 | A2 | | | ALL |
| 0304 | 20 | | GK | | 4-0 | 36-11-11 | D05142 | | B1 | | TB0166Z | 17 | BJ | | 115-199 |
| 0305 | 20 | | GK | | 4-0 | 36-11-11 | D05142 | | C1 | | GD01686 | DC.. | 2 | | ALL |
| 0306 | 20 | | GK | | 7-0 | 36-11-11 | D05142 | | X1 | * | D40874J | 31 | | | 001-099 |
| 0306 | 20 | | GK | | 4-0 | 36-11-11 | D05142 | | X1 | | TB0166Y | A010 | BJ | | 115-199 |
| 0307 | 20 | | GK | | 4-0 | 36-11-11 | D05142 | | X2 | | TB0166A | A009 | 2 | | 001-099 |
| 0307 | 20 | | GK | | 4-0 | 36-11-11 | D05142 | | X2 | | TB0166A | A018 | 2 | | 115-199 |
| 0308 | 20 | | GK | | 1-0 | 36-11-11 | D05142 | | B2 | * | D05142 | X1 | | * | 001-099 |
| 0308 | 20 | | GK | | 4-0 | 36-11-11 | D05142 | | B2 | | TB0166Y | A010 | BJ | | 115-199 |
| 0309 | 20 | | GK | | 3-0 | 36-11-11 | D05142 | | C2 | | TB0166A | A009 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 9

Oct 09/2008



WIRE LIST

91-21-11

Section W1260

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0335 | 20 | | GK | | 8-0 | 36-11-11 | D02532 | | X2 | | D41948J | | 8 | | 115-199 |
| 0336 | 20 | | GK | | 1-0 | 36-11-11 | D02528 | | B2 | * | D02528 | | X1 | * | 001-099 |
| 0336 | 20 | | GK | | 4-0 | 36-11-11 | TB0166Z | | 17 | BJ | D02528 | | X1 | | 115-199 |
| 0337 | 20 | | GK | | 3-0 | 36-11-11 | D02528 | | X2 | | GD01686 | DC.. | 2 | | 001-099 |
| 0337 | 20 | | GK | | 4-0 | 36-11-11 | D02528 | | X2 | | GD01686 | DC.. | 2 | | 115-199 |
| 0338 | 20 | | GK | | 4-0 | 36-11-11 | TB0166Y | A009 | BJ | | D02530 | | X1 | | 115-199 |
| 0339 | 20 | | GK | | 4-0 | 36-11-11 | D02532 | | X1 | | D05142 | | B2 | * | 001-099 |
| 0339 | 20 | | GK | | 4-0 | 36-11-11 | D02532 | | X1 | | TB0166Y | A010 | BJ | | 115-199 |
| 0340 | 20 | | GK | | 4-0 | 36-11-11 | D02530 | | X2 | | GD01686 | DC.. | 2 | | ALL |
| 0341 | 20 | | GK | | 8-0 | 36-11-12 | D02528 | | B3 | | D40060J | | 14 | | 001-099 |
| 0341 | 20 | | GK | | 9-0 | 36-11-12 | D02528 | | B3 | | D40060J | | 14 | | 115-199 |
| 0342 | 20 | | GK | | 8-0 | 36-11-12 | D02530 | | B3 | | D40060J | | 15 | | 001-099 |
| 0342 | 20 | | GK | | 9-0 | 36-11-12 | D02530 | | B3 | | D40060J | | 15 | | 115-199 |
| 0343 | 24 | | GK | | 8-0 | 36-11-41 | D04116 | | 6 | | D05258 | | B3 | * | 001-009 |
| 0343 | 24 | | GK | | 8-0 | 36-11-41 | D04116 | | 6 | | D07036 | | A2 | * | 010-099 |
| 0343 | 24 | | GK | | 8-0 | 36-11-41 | D04116 | | 6 | | TB0168Y | C013 | BJ | | 115-199 |
| 0344 | 24 | | GK | | 7-0 | 36-11-41 | D04116 | | 8 | | D41022J | | 31 | | 001-099 |
| 0344 | 24 | | GK | | 6-0 | 36-11-41 | D04116 | | 8 | | D41022J | | 31 | | 115-199 |
| 0345 | 24 | | GK | | 4-0 | 30-31-11 | D04242 | | A1 | | GD01685 | AC.. | 2 | | ALL |
| 0346 | 24 | | GK | | 9-0 | 30-31-11 | D04242 | | A2 | | TB0168Y | A012 | BJ | | 001-099 |
| 0346 | 24 | | GK | | 8-0 | 30-31-11 | D04242 | | A2 | | TB0168Y | A012 | BJ | | 115-199 |
| 0347 | 24 | | GK | | 7-0 | 30-31-11 | D04312 | | A2 | | TB0168Y | A012 | BJ | | 001-099 |
| 0347 | 24 | | GK | | 9-0 | 30-31-11 | D04312 | | A2 | | TB0168Y | A012 | BJ | | 115-199 |
| 0348 | 24 | | GK | | 4-0 | 30-31-11 | D04312 | | A1 | | GD01671 | AC.. | 2 | | 001-099 |
| 0348 | 24 | | GK | | 4-0 | 30-31-11 | D04312 | | A1 | | GD01670 | AC.. | 2 | | 115-199 |
| 0349 | 22 | | GK | | 8-0 | 30-32-11 | D40874J | | 19 | | D04242 | | B1 | * | 001-099 |
| 0349 | 22 | | GK | | 8-0 | 30-32-11 | D40874J | | 19 | | TB0165Y | A011 | BJ | | 115-199 |
| 0350 | 22 | | GK | | 10-0 | 30-32-11 | D04242 | | B1 | * | D04312 | | B1 | * | 001-099 |
| 0350 | 22 | | GK | | 8-0 | 30-32-11 | D04242 | | B1 | | TB0165Y | A011 | BJ | | 115-199 |
| 0351 | 22 | | GK | | 2-0 | 30-32-11 | D04312 | | B1 | * | D00592 | | C3 | * | 001-099 |
| 0351 | 22 | | GK | | 9-0 | 30-32-11 | D04312 | | B1 | | TB0165Y | A011 | BJ | | 115-199 |
| 0352 | 22 | | GK | | 10-0 | 30-32-11 | D04242 | | B2 | | TB0160Z | | 11 | BJ | 001-099 |
| 0352 | 22 | | GK | | 4-0 | 30-32-11 | D04242 | | B2 | | TB0165Y | C011 | BJ | | 115-199 |
| 0353 | 22 | | GK | | 4-0 | 30-32-11 | D04312 | | B2 | | TB0160Z | | 11 | BJ | 001-099 |
| 0353 | 22 | | GK | | 9-0 | 30-32-11 | D04312 | | B2 | | TB0165Y | C011 | BJ | | 115-199 |
| 0354 | 22 | | GK | | 7-0 | 30-32-11 | D40874J | | 20 | | TB0160Z | | 11 | BJ | 001-099 |
| 0354 | 22 | | GK | | 6-0 | 30-32-11 | D40874J | | 20 | | TB0165Y | C011 | BJ | | 115-199 |
| 0355 | 22 | | GK | | 7-0 | 30-32-11 | D41473J | | 17 | | TB0160Z | | 11 | BJ | 001-099 |
| 0355 | 22 | | GK | | 8-0 | 30-32-11 | D41473J | | 17 | | TB0165Y | C011 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 0356 | 20 | GK | | | 9-0 | 74-31-11 | D40696J | 46 | | | TB0165Y | A012 | BJ | | 115-199 |
| 0357 | 20 | GK | | | 7-0 | 74-31-11 | TB0165Y | A003 | BJ | | D41938J | 1 | | | 115-199 |
| 0358 | 20 | GK | | | 8-0 | 74-31-11 | D41938J | 2 | | | TB0166Y | A018 | BJ | | 001-099 |
| 0358 | 20 | GK | | | 4-0 | 74-31-11 | D02520 | A2 | | | TB0165Y | C012 | BJ | | 115-199 |
| 0359 | 20 | GK | | | 2-0 | 74-31-11 | D04584 | D1 | | | TB0166Y | A018 | BJ | | 001-099 |
| 0359 | 20 | GK | | | 4-0 | 74-31-11 | D04584 | D1 | | | TB0165Y | C012 | BJ | | 115-199 |
| 0360 | 20 | GK | | | 8-0 | 74-31-11 | D41938J | 7 | | | TB0166Y | A018 | BJ | | 001-099 |
| 0360 | 20 | GK | | | 7-0 | 74-31-11 | D41938J | 7 | | | TB0165Y | C012 | BJ | | 115-199 |
| 0361 | 20 | GK | | | 8-0 | 74-31-11 | D02520 | A1 | | | D41938J | 2 | | | 115-199 |
| 0362 | 20 | GK | | | 4-0 | 74-31-11 | D02520 | X1 | | | TB0165Y | A013 | BJ | | 115-199 |
| 0363 | 20 | GK | | | 4-0 | 74-31-11 | D02522 | X1 | | | TB0165Y | A013 | BJ | | 115-199 |
| 0364 | 20 | GK | | | 4-0 | 74-31-11 | D02520 | X2 | | | GD01683 | DC.. | 2 | | 115-199 |
| 0365 | 20 | GK | | | 7-0 | 74-31-11 | TB0165Y | C003 | BJ | | D41958J | 5 | | | 115-199 |
| 0366 | 20 | GK | | | 8-0 | 74-31-11 | D41958J | 6 | | | TB0166Y | C018 | BJ | | 001-099 |
| 0366 | 20 | GK | | | 8-0 | 74-31-11 | D02522 | A2 | | | TB0165Y | C013 | BJ | | 115-199 |
| 0367 | 20 | GK | | | 2-0 | 74-31-11 | D04584 | A1 | | | TB0166Y | C018 | BJ | | 001-099 |
| 0367 | 20 | GK | | | 4-0 | 74-31-11 | D04584 | A1 | | | TB0165Y | C013 | BJ | | 115-199 |
| 0368 | 20 | GK | | | 8-0 | 74-31-11 | D41958J | 11 | | | TB0166Y | C018 | BJ | | 001-099 |
| 0368 | 20 | GK | | | 7-0 | 74-31-11 | D41958J | 11 | | | TB0165Y | C013 | BJ | | 115-199 |
| 0369 | 20 | GK | | | 7-0 | 74-31-11 | D04584 | X2 | | | D41497J | 36 | | | 001-099 |
| 0369 | 20 | GK | | | 4-0 | 74-31-11 | D04584 | X2 | | | TB0165Y | A014 | BJ | | 115-199 |
| 0370 | 20 | GK | | | 8-0 | 74-31-11 | D41473J | 30 | | | TB0165Y | A014 | BJ | | 115-199 |
| 0371 | 20 | GK | | | 8-0 | 74-31-11 | D41473J | 38 | | | TB0165Y | A014 | BJ | | 115-199 |
| 0372 | 24 | GK | | | 4-0 | 74-31-11 | GD01685 | DC.. | 2 | | D04306 | A3 | | | 001-099 |
| 0372 | 24 | GK | | | 4-0 | 74-31-11 | GD01684 | DC.. | 2 | | D04306 | A3 | | | 115-199 |
| 0373 | 20 | GK | | | 8-0 | 74-31-11 | D04306 | B3 | | | D40728J | 29 | | | ALL |
| 0374 | 20 | GK | | | 8-0 | 74-31-11 | D04306 | B2 | | | D41938J | 13 | | | ALL |
| 0375 | 20 | GK | | | 8-0 | 74-31-11 | D04306 | B1 | | * | D40696J | 46 | | | 001-099 |
| 0375 | 20 | GK | | | 4-0 | 74-31-11 | D04306 | B1 | | | TB0165Y | A012 | BJ | | 115-199 |
| 0376 | 20 | GK | | | 1-0 | 74-31-11 | D04306 | X1 | | | D04306 | B1 | | * | 001-099 |
| 0376 | 20 | GK | | | 4-0 | 74-31-11 | D04306 | X1 | | | TB0165Y | A012 | BJ | | 115-199 |
| 0377 | 20 | GK | | | 4-0 | 74-31-11 | D04306 | X2 | | | GD01685 | AC.. | 2 | | 001-099 |
| 0377 | 20 | GK | | | 4-0 | 74-31-11 | D04306 | X2 | | | GD01684 | AC.. | 2 | | 115-199 |
| 0378 | 20 | GK | | | 4-0 | 74-31-11 | D02522 | X2 | | | GD01683 | DC.. | 2 | | 115-199 |
| 0379 | 16 | GK | | | 8-0 | 75-31-11 | D40728J | 21 | | | TB0165G | 15 | 2 | | 001-099 |
| 0379 | 16 | GK | | | 10-0 | 75-31-11 | D40728J | 21 | | | TB0165G | 15 | 2 | | 115-199 |
| 0380 | 16 | GK | | | 7-0 | 75-31-11 | D41988J | 1 | | | TB0165G | 15 | 2 | | 001-099 |
| 0380 | 16 | GK | | | 8-0 | 75-31-11 | TB0165G | 15 | 2 | | D41988J | 1 | | | 115-199 |
| 0381 | 16 | GK | | | 3-0 | 75-31-11 | D02700 | A2 | | | TB0165G | 15 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0381 | 16 | | GK | | 4-0 | 75-31-11 | D02700 | | A2 | | TB0165G | 15 | 2 | | 115-199 |
| 0382 | 18 | | GK | | 8-0 | 75-31-11 | D41988J | | 2 | | D02700 | A1 | | | 001-099 |
| 0382 | 18 | | GK | | 7-0 | 75-31-11 | D02700 | | A1 | | D41988J | 2 | | | 115-199 |
| 0383 | 22 | | GK | | 9-0 | 76-11-11 | D02700 | | B2 | | D41948J | 39 | | | 001-099 |
| 0383 | 22 | | GK | | 7-0 | 76-11-11 | D02700 | | B2 | | D41948J | 3 | | | 115-199 |
| 0384 | 20 | | GK | | 4-0 | 76-11-11 | D02154 | | 4 | | D02708 | X2 | | * | 001-099 |
| 0384 | 20 | | GK | | 4-0 | 76-11-11 | D02154 | | 4 | | TB0165Y | A017 | BJ | | 115-199 |
| 0385 | 20 | | GK | | 3-0 | 76-11-11 | D02154 | | 2 | | GD01684 | DC.. | 2 | | 001-099 |
| 0385 | 20 | | GK | | 4-0 | 76-11-11 | D02154 | | 2 | | GD01684 | DC.. | 2 | | 115-199 |
| 0386 | 24 | | GK | | 8-0 | 76-11-11 | D02154 | | 5 | | D41948J | 17 | | | 115-199 |
| 0387 | 24 | | GK | | 4-0 | 76-11-11 | D02154 | | 6 | | TB0166Y | A019 | BJ | | 001-099 |
| 0387 | 24 | | GK | | 4-0 | 76-11-11 | D02154 | | 6 | | TB0165Y | C014 | BJ | | 115-199 |
| 0388 | 24 | | GK | | 8-0 | 76-11-11 | D41948J | | 4 | | TB0166Y | A019 | BJ | | 001-099 |
| 0388 | 24 | | GK | | 7-0 | 76-11-11 | D41948J | | 4 | | TB0165Y | C014 | BJ | | 115-199 |
| 0389 | 24 | | GK | | 8-0 | 76-11-11 | D41948J | | 18 | | TB0166Y | A019 | BJ | | 001-099 |
| 0389 | 24 | | GK | | 7-0 | 76-11-11 | D41948J | | 18 | | TB0165Y | C014 | BJ | | 115-199 |
| 0390 | 22 | | GK | | 8-0 | 76-11-11 | D41948J | | 1 | | D02154 | 1 | | | 115-199 |
| 0391 | 22 | | GK | | 3-0 | 76-11-11 | D02154 | | 7 | | GD01684 | DC.. | 2 | | 001-099 |
| 0391 | 22 | | GK | | 4-0 | 76-11-11 | D02154 | | 7 | | GD01684 | DC.. | 2 | | 115-199 |
| 0393 | 22 | | GK | | 9-0 | 76-11-11 | D02700 | | C1 | | D41958J | 4 | | | 001-099 |
| 0393 | 22 | | GK | | 8-0 | 76-11-11 | D02700 | | C1 | | D41958J | 4 | | | 115-199 |
| 0394 | 22 | | GK | | 9-0 | 76-11-11 | D02700 | | B1 | | D41958J | 3 | | | 001-099 |
| 0394 | 22 | | GK | | 8-0 | 76-11-11 | D02700 | | B1 | | D41958J | 3 | | | 115-199 |
| 0395 | 22 | | GK | | 9-0 | 76-11-11 | D02154 | | 8 | | D41948J | 2 | | | 001-099 |
| 0395 | 22 | | GK | | 8-0 | 76-11-11 | SM00047 | | | WI | D41948J | 2 | | | 115-199 |
| 0397 | 22 | | GK | | 4-0 | SPARE | D02158 | | 7 | | GD01684 | DC.. | 2 | | 115-199 |
| 0400 | 22 | | GK | | 10-0 | 76-11-21 | D04322 | | 6 | | TB0360X | B010 | BJ | | 001-099 |
| 0400 | 22 | | GK | | 8-0 | 76-11-21 | D04322 | | 6 | | TB0360X | B010 | BJ | | 115-199 |
| 0403 | 22 | | GK | | 9-0 | 76-11-21 | D04322 | | 1 | | TB0168Z | 6 | BJ | | 001-099 |
| 0403 | 22 | | GK | | 8-0 | 76-11-21 | D04322 | | 1 | | TB0168Z | 6 | BJ | | 115-199 |
| 0404 | 22 | | GK | | 9-0 | 76-11-21 | D04322 | | 7 | | TB0168Z | 6 | BJ | | 001-099 |
| 0404 | 22 | | GK | | 8-0 | 76-11-21 | D04322 | | 7 | | TB0168Z | 6 | BJ | | 115-199 |
| 0405 | 22 | | GK | | 10-0 | 76-11-21 | D04322 | | 3 | | TB0360X | D009 | BJ | | 001-099 |
| 0405 | 22 | | GK | | 9-0 | 76-11-21 | D04322 | | 3 | | TB0360X | D009 | BJ | | 115-199 |
| 0406 | 22 | | GK | | 5-0 | 76-11-21 | D40696J | | 10 | | TB0168Z | 6 | BJ | | 001-099 |
| 0406 | 22 | | GK | | 6-0 | 76-11-21 | D40696J | | 10 | | TB0168Z | 6 | BJ | | 115-199 |
| 0407 | 22 | | GK | | 8-0 | 77-12-41 | D41850J | | 22 | | D04312 | X1 | | * | 001-099 |
| 0407 | 22 | | GK | | 3-0 | 77-12-41 | D41850J | | 22 | | SM00021 | | WI | | 115-199 |
| 0408 | 22 | | GK | | 7-0 | 77-12-41 | D41948J | | 13 | | SM00021 | | WI | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|------|--|---------|-------|------|------|---------|-------|------|------|---------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0411 | 22 | | GK | 7-0 | 77-12-42 | D04242 | | X1 | | D42096J | 5 | | | ALL | | |
| 0412 | 22 | | GK | 4-0 | 77-12-42 | D04242 | | X2 | | GD01685 | DC.. | 2 | | 001-099 | | |
| 0412 | 22 | | GK | 4-0 | 77-12-42 | D04242 | | X2 | | GD01684 | DC.. | 2 | | 115-199 | | |
| 0413 | 22 | | GK | 7-0 | 78-34-11 | D02746 | | A3 | | TB0163Z | 6 | BJ | | 001-002 | | |
| 0413 | 22 | | GK | 3-0 | 78-34-11 | D02746 | | A3 | | TB0165Y | A018 | BJ | | 003-099 | | |
| 0413 | 22 | | GK | 4-0 | 78-34-11 | D02746 | | A3 | | TB0165Y | A018 | BJ | | 115-199 | | |
| 0414 | 22 | | GK | 7-0 | 78-34-11 | D41462J | | 17 | | M10004 | A | C | | 003-099 | | |
| 0415 | 22 | | GK | 8-0 | 78-34-11 | D41938J | | 3 | | TB0163Z | 6 | BJ | | 001-002 | | |
| 0415 | 22 | | GK | 8-0 | 78-34-11 | D41938J | | 3 | | TB0165Y | A018 | BJ | | 003-099 | | |
| 0415 | 22 | | GK | 7-0 | 78-34-11 | D41938J | | 3 | | TB0165Y | A018 | BJ | | 115-199 | | |
| 0416 | 22 | | GK | 8-0 | 78-34-11 | D02746 | | A2 | | TB0168Y | A015 | BJ | | 115-199 | | |
| 0417 | 22 | | GK | 10-0 | 78-34-11 | D02746 | | X1 | * | D00598 | A2 | | * | 001-099 | | |
| 0417 | 22 | | GK | 8-0 | 78-34-11 | D02746 | | X1 | | TB0168Y | A015 | BJ | | 115-199 | | |
| 0418 | 22 | | GK | 7-0 | 78-34-11 | D02746 | | X2 | | D41948J | 5 | | | 001-099 | | |
| 0418 | 22 | | GK | 8-0 | 78-34-11 | D02746 | | X2 | | D41948J | 5 | | | 115-199 | | |
| 0422 | 24 | | GK | 1-0 | 78-36-11 | D41958J | | 43 | | D41958J | 10 | | | 003-099 | | |
| 0426 | 24 | | GK | 7-0 | 78-36-11 | D40728J | | 28 | | TB0166Y | C006 | BJ | | 001-002 | | |
| 0426 | 24 | | GK | 2-0 | 78-36-11 | D40728J | | 28 | | SM00038 | | WI | | 003-099 | | |
| 0426 | 24 | | GK | 6-0 | 78-36-11 | D40728J | | 28 | | TB0165Y | A019 | BJ | | 115-199 | | |
| 0427 | 24 | | GK | 7-0 | 78-36-11 | D41958J | | 38 | | TB0166Y | C006 | BJ | | 001-002 | | |
| 0427 | 24 | | GK | 3-0 | 78-36-11 | D41958J | | 38 | | SM00038 | | WI | | 003-099 | | |
| 0427 | 24 | | GK | 7-0 | 78-36-11 | D41958J | | 22 | | TB0165Y | A019 | BJ | | 115-199 | | |
| 0432 | 24 | | GK | 8-0 | 78-36-11 | D41958J | | 9 | | D41958J | 10 | | | 001-002 | | |
| 0432 | 24 | | GK | 5-0 | 78-36-11 | D41958J | | 9 | | D41462J | 21 | | | 003-099 | | |
| 0432 | 24 | | GK | 7-0 | 78-36-11 | D41958J | | 9 | | D41958J | 10 | | | 115-199 | | |
| 0440 | 20 | | GK | 7-0 | 80-11-11 | D40728J | | 18 | | TB0166Z | 7 | BJ | | ALL | | |
| 0441 | 20 | | GK | 3-0 | 74-31-11 | D04584 | | X1 | | TB0166Z | 7 | BJ | | 001-099 | | |
| 0441 | 20 | | GK | 4-0 | 80-11-11 | D04584 | | X1 | | TB0166Z | 7 | BJ | | 115-199 | | |
| 0442 | 20 | | GK | 3-0 | 80-11-11 | D02708 | | X1 | | TB0166Z | 7 | BJ | | 001-099 | | |
| 0442 | 20 | | GK | 4-0 | 80-11-11 | D02708 | | X1 | | TB0166Z | 7 | BJ | | 115-199 | | |
| 0443 | 20 | | GK | 3-0 | 80-11-11 | D02702 | | 6 | | TB0166Z | 7 | BJ | | 001-099 | | |
| 0443 | 20 | | GK | 4-0 | 80-11-11 | D02702 | | 6 | | TB0166Z | 7 | BJ | | 115-199 | | |
| 0444 | 20 | | GK | 4-0 | 80-11-11 | D02990 | | X1 | | TB0166Z | 7 | BJ | | 115-199 | | |
| 0445 | 20 | | GK | 4-0 | 80-11-11 | D02990 | | A2 | | TB0166Z | 7 | BJ | | 115-199 | | |
| 0446 | 20 | | GK | 2-0 | 80-11-11 | D02708 | | X2 | * | D02994 | 10 | | | 001-099 | | |
| 0446 | 20 | | GK | 4-0 | 80-11-11 | D02708 | | X2 | | TB0165Y | A017 | BJ | | 115-199 | | |
| 0447 | 20 | | GK | 4-0 | 80-11-11 | D02994 | | 10 | | TB0165Y | A017 | BJ | | 115-199 | | |
| 0448 | 20 | | GK | 4-0 | 80-11-11 | D02992 | | X1 | | TB0166Y | A006 | BJ | | ALL | | |
| 0449 | 20 | | GK | 4-0 | 80-11-11 | D02994 | | 6 | | TB0166Y | A006 | BJ | | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0450 | 20 | | GK | | 8-0 | 80-11-11 | D41958J | | 15 | | TB0166Y | A006 | BJ | | 001-099 |
| 0450 | 20 | | GK | | 7-0 | 80-11-11 | D41958J | | 15 | | TB0166Y | A006 | BJ | | 115-199 |
| 0451 | 20 | | GK | | 8-0 | 80-11-11 | D41938J | | 5 | | TB0166Y | A006 | BJ | | 001-099 |
| 0451 | 20 | | GK | | 7-0 | 80-11-11 | D41938J | | 5 | | TB0166Y | A006 | BJ | | 115-199 |
| 0452 | 20 | | GK | | 4-0 | 80-11-11 | D02992 | | X2 | | GD01687 | DC.. | 2 | | ALL |
| 0453 | 20 | | GK | | 4-0 | 80-11-11 | D02994 | | 11 | | GD01687 | DC.. | 2 | | ALL |
| 0454 | 24 | | GK | | 3-0 | 80-11-11 | D02994 | | 14 | | D02702 | | 8 | | 001-099 |
| 0454 | 20 | | GK | | 4-0 | 80-11-11 | D02994 | | 14 | | D02702 | | 8 | | 115-199 |
| 0455 | 24 | | GK | | 9-0 | 80-11-11 | D02994 | | 7 | | TB0168A | C003 | 2 | | 001-099 |
| 0455 | 20 | | GK | | 4-0 | 80-11-11 | D02994 | | 7 | | TB0166A | C015 | 2 | | 115-199 |
| 0456 | 24 | | GK | | 9-0 | 80-11-11 | D02702 | | 4 | | TB0168Y | A004 | BJ | | 001-099 |
| 0456 | 24 | | GK | | 8-0 | 80-11-11 | D02702 | | 4 | | TB0168Y | C015 | BJ | | 115-199 |
| 0457 | 24 | | GK | | 3-0 | 80-11-11 | D02994 | | 8 | | D02702 | | 14 | | 001-099 |
| 0457 | 24 | | GK | | 4-0 | 80-11-11 | D02994 | | 8 | | D02702 | | 14 | | 115-199 |
| 0458 | 24 | | GK | | 7-0 | 80-11-11 | D41948J | | 9 | | D02702 | | 5 | | 001-099 |
| 0458 | 24 | | GK | | 8-0 | 80-11-11 | D41948J | | 9 | | D02702 | | 5 | | 115-199 |
| 0459 | 20 | | GK | | 3-0 | 80-11-11 | D02700 | | C2 | | TB0166Y | A005 | BJ | | 001-099 |
| 0459 | 20 | | GK | | 4-0 | 80-11-11 | D02700 | | C2 | | TB0166Y | C006 | BJ | | 115-199 |
| 0461 | 20 | | GK | | 8-0 | 80-11-11 | D41958J | | 14 | | TB0166Y | A005 | BJ | | 001-099 |
| 0461 | 20 | | GK | | 7-0 | 80-11-11 | D41958J | | 14 | | TB0166Y | C006 | BJ | | 115-199 |
| 0462 | 20 | | GK | | 8-0 | 80-11-11 | D41938J | | 4 | | D02990 | X2 | | | 115-199 |
| 0463 | 20 | | GK | | 4-0 | 80-11-11 | D02994 | | 12 | | GD01687 | DC.. | 2 | | ALL |
| 0464 | 20 | | GK | | 4-0 | 80-11-11 | D02700 | | X2 | | GD01685 | DC.. | 2 | | ALL |
| 0465 | 20 | | GK | | 3-0 | 80-11-11 | D02700 | | X1 | | TB0166Y | A005 | BJ | | 001-099 |
| 0465 | 20 | | GK | | 4-0 | 80-11-11 | D02700 | | X1 | | TB0166Y | C006 | BJ | | 115-199 |
| 0466 | 20 | | GK | | 8-0 | 80-11-11 | D02702 | | 12 | | D41938J | | 6 | | ALL |
| 0467 | 24 | | GK | | 3-0 | 80-11-11 | D02702 | | 7 | | GD01685 | DC.. | 2 | | 001-099 |
| 0467 | 20 | | GK | | 4-0 | 80-11-11 | D02702 | | 7 | | GD01685 | DC.. | 2 | | 115-199 |
| 0468 | 20 | | GK | | 8-0 | 80-11-11 | TB0166Z | | 7 | BJ | D41958J | | 13 | | 001-099 |
| 0468 | 20 | | GK | | 8-0 | 80-11-11 | D02990 | | A1 | | D41958J | | 13 | | 115-199 |
| 0469 | 20 | | GK | | 4-0 | 80-11-11 | D02990 | | A3 | | TB0165Y | A013 | BJ | | 115-199 |
| 0470 | 24 | | GK | | 8-0 | 74-31-11 | D04306 | | A2 | | D41948J | | 24 | | 001-099 |
| 0470 | 24 | | GK | | 8-0 | 74-31-11 | D04306 | | A2 | | D41938J | | 12 | | 115-199 |
| 0471 | 20 | | GK | | 8-0 | 74-31-11 | D02522 | | A1 | | D41958J | | 6 | | 115-199 |
| 0473 | 22 | | GK | | 8-0 | 77-12-41 | D04312 | | X1 | * | D41948J | | 13 | | 001-099 |
| 0473 | 22 | | GK | | 6-0 | 77-12-41 | D04312 | | X1 | | SM00021 | | WI | | 115-199 |
| 0474 | 22 | | GK | | 4-0 | 77-12-41 | D04312 | | X2 | | GD01671 | DC.. | 2 | | 001-099 |
| 0474 | 22 | | GK | | 4-0 | 77-12-41 | D04312 | | X2 | | GD01670 | DC.. | 2 | | 115-199 |
| 0475 | 20 | | GK | | 4-0 | 36-11-11 | D02994 | | 5 | | TB0166Z | | 12 | BJ | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0475 | 20 | | GK | | 4-0 | 36-11-11 | D02994 | | 5 | | TB0166Z | 16 | BJ | | 115-199 |
| 0476 | 20 | | GK | | 8-0 | 36-11-11 | D02994 | | 4 | | D07036 | C1 | | * | 001-099 |
| 0476 | 20 | | GK | | 4-0 | 36-11-11 | D02994 | | 4 | | TB0165Y | C002 | BJ | | 115-199 |
| 0477 | 20 | | GK | | 10-0 | 36-11-11 | D02994 | | 3 | | D07046 | 11 | | | ALL |
| 0478 | 20 | | GK | | 2-0 | 36-11-11 | D04116 | | 3 | | GD01683 | DC.. | 2 | | 001-099 |
| 0478 | 20 | | GK | | 4-0 | 36-11-11 | D04116 | | 3 | | GD01684 | DC.. | 2 | | 115-199 |
| 0479 | 20 | | GK | | 2-0 | 74-31-11 | D04584 | | A2 | | TB0166Y | C004 | BJ | | 001-099 |
| 0479 | 20 | | GK | | 4-0 | 74-31-11 | D04584 | | A2 | | TB0165Y | C008 | BJ | | 115-199 |
| 0480 | 22 | | GK | | 2-0 | 74-31-11 | D04584 | | D2 | | TB0166Y | A004 | BJ | | 001-099 |
| 0480 | 22 | | GK | | 4-0 | 74-31-11 | D04584 | | D2 | | TB0165Y | A008 | BJ | | 115-199 |
| 0481 | 22 | | GK | | 9-0 | 30-21-11 | D02992 | | C2 | | TB0168Y | C016 | BJ | | 001-099 |
| 0481 | 22 | | GK | | 8-0 | 30-21-11 | D02992 | | C2 | | TB0168Y | C016 | BJ | | 115-199 |
| 0482 | 22 | | GK | | 9-0 | 30-21-11 | D41958J | | 21 | | D02992 | C3 | | | 001-099 |
| 0482 | 22 | | GK | | 8-0 | 30-21-11 | D41958J | | 21 | | D02992 | C3 | | | 115-199 |
| 0483 | 20 | | GK | | 7-0 | 32-35-11 | D04354 | | 11 | | D41948J | 16 | | | 001-099 |
| 0483 | 20 | | GK | | 8-0 | 32-35-11 | D04354 | | 11 | | D41948J | 16 | | | 115-199 |
| 0484 | 20 | | GK | | 8-0 | 32-35-11 | D04354 | | 10 | | K10369 | X1 | C | * | 001-099 |
| 0484 | 20 | | GK | | 8-0 | 32-35-11 | D04354 | | 10 | | TB0168Y | A020 | BJ | | 115-199 |
| 0485 | 20 | | GK | | 8-0 | 32-35-11 | D04354 | | 6 | | K10369 | X1 | C | * | 001-099 |
| 0485 | 20 | | GK | | 8-0 | 32-35-11 | D04354 | | 6 | | TB0168Y | A020 | BJ | | 115-199 |
| 0486 | 20 | | GK | | 8-0 | 32-35-11 | D41958J | | 32 | | TB0360A | C014 | 2 | | 001-099 |
| 0486 | 20 | | GK | | 7-0 | 32-35-11 | D41958J | | 32 | | TB0168Y | A020 | BJ | | 115-199 |
| 0487 | 20 | | GK | | 4-0 | 32-35-11 | D04354 | | 12 | | GD01686 | DC.. | 2 | | ALL |
| 0488 | 22 | | GK | | 7-0 | 49-61-11 | D04394 | | B1 | | D42080J | 1 | | | 001-099 |
| 0488 | 22 | | GK | | 8-0 | 49-61-11 | D04394 | | B1 | | D42080J | 1 | | | 115-199 |
| 0489 | 22 | | GK | | 7-0 | 49-61-11 | D04394 | | B2 | | D42080J | 2 | | | 001-099 |
| 0489 | 22 | | GK | | 8-0 | 49-61-11 | D04394 | | B2 | | D42080J | 2 | | | 115-199 |
| 0490 | 22 | | GK | | 7-0 | 49-61-11 | D04394 | | B3 | | D42080J | 3 | | | 001-099 |
| 0490 | 22 | | GK | | 8-0 | 49-61-11 | D04394 | | B3 | | D42080J | 3 | | | 115-199 |
| 0491 | 22 | | GK | | 8-0 | 49-61-11 | D02992 | | B1 | | D42080J | 5 | | | ALL |
| 0492 | 22 | | GK | | 8-0 | 49-61-11 | D02992 | | B2 | | D42080J | 4 | | | ALL |
| 0495 | 16 | | GK | | 7-0 | 29-11-22 | D40874J | | 27 | 16 | TB0166G | 25 | 2 | | 001-099 |
| 0495 | 16 | | GK | | 8-0 | 29-11-22 | D40874J | | 27 | 16 | TB0165G | 16 | 2 | | 115-199 |
| 0496 | 16 | | GK | | 7-0 | 29-11-22 | D40542J | | 2 | 16 | D03076 | A1 | | | 001-099 |
| 0496 | 16 | | GK | | 8-0 | 29-11-22 | D40542J | | 2 | 16 | D03076 | A1 | | | 115-199 |
| 0497 | 22 | | GK | | 8-0 | 29-11-22 | D40874J | | 26 | | D03076 | X1 | | * | 001-099 |
| 0497 | 22 | | GK | | 8-0 | 29-11-22 | TB0168Y | A011 | BJ | | D03076 | X1 | | | 115-199 |
| 0498 | 20 | | GK | | 3-0 | 29-11-22 | D03076 | | X2 | | D05662 | A2 | | | 001-099 |
| 0498 | 20 | | GK | | 3-0 | 29-11-22 | D05662 | | A2 | | D03076 | X2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0499 | 16 | | GK | | 8-0 | 29-11-31 | D40608J | | 21 | | D03072 | | A2 | | 001-099 |
| 0499 | 16 | | GK | | 9-0 | 29-11-31 | D40608J | | 4 | 16 | D03072 | | A2 | | 115-199 |
| 0500 | 16 | | GK | | 8-0 | 29-11-31 | D40608J | | 23 | | D03072 | | A1 | | 001-099 |
| 0500 | 16 | | GK | | 10-0 | 29-11-31 | D40608J | | 5 | 16 | D03072 | | A1 | | 115-199 |
| 0501 | 20 | | GK | | 3-0 | 29-11-31 | D05654 | | A2 | | D03072 | | X2 | | 001-099 |
| 0501 | 22 | | GK | | 3-0 | 29-11-31 | D05654 | | A2 | | D03072 | | X2 | | 115-199 |
| 0502 | 22 | | GK | | 8-0 | 29-11-31 | D40608J | | 6 | | D03072 | | X1 | | 001-099 |
| 0502 | 22 | | GK | | 10-0 | 29-11-31 | D40608J | | 6 | | D03072 | | X1 | | 115-199 |
| 0504 | 22 | | GK | | 10-0 | 32-61-21 | D04354 | | 5 | | D41958J | | 33 | | 001-099 |
| 0504 | 22 | | GK | | 8-0 | 32-61-21 | D04354 | | 5 | | D41958J | | 33 | | 115-199 |
| 0505 | 24 | | GK | | 8-0 | 26-15-11 | D41948J | | 21 | | TB0166A | A011 | 2 | | 001-099 |
| 0505 | 24 | | GK | | 6-0 | 26-15-11 | D41948J | | 21 | | TB0165C | A021 | 2 | | 115-199 |
| 0506 | 24 | | GK | | 2-0 | 26-15-11 | TB0165C | C021 | 2 | | TB0165Y | C019 | BJ | | 115-199 |
| 0507 | 24 | | GK | | 3-0 | 26-15-11 | D04394 | | X1 | | TB0166A | C024 | 2 | *2 | 001-099 |
| 0507 | 24 | | GK | | 4-0 | 26-15-11 | D04394 | | X1 | | TB0165Y | C019 | BJ | | 115-199 |
| 0508 | 24 | | GK | | 1-0 | 26-15-11 | TB0166A | C024 | 2 | *1 | TB0166A | C011 | 2 | | 001-099 |
| 0508 | 24 | | GK | | 2-0 | 26-15-11 | TB0165C | C022 | 2 | | TB0165Y | C019 | BJ | | 115-199 |
| 0509 | 24 | | GK | | 3-0 | 26-15-11 | D04398 | | 7 | | TB0166A | C024 | 2 | *1 | 001-099 |
| 0509 | 24 | | GK | | 2-0 | 26-15-11 | D04398 | | 7 | | TB0165Y | C019 | BJ | | 115-199 |
| 0510 | 24 | | GK | | 4-0 | 26-15-11 | D04400 | | 7 | | TB0166A | C024 | 2 | *2 | 001-099 |
| 0510 | 24 | | GK | | 2-0 | 26-15-11 | D04400 | | 7 | | TB0165C | C022 | 2 | | 115-199 |
| 0511 | 24 | | GK | | 8-0 | 26-15-11 | D41958J | | 36 | | TB0166A | A024 | 2 | | 001-099 |
| 0511 | 24 | | GK | | 7-0 | 26-15-11 | D41958J | | 25 | | TB0165C | A022 | 2 | | 115-199 |
| 0512 | 24 | | GK | | 3-0 | 26-15-11 | D04396 | | X2 | | TB0165A | C005 | 2 | | 001-099 |
| 0512 | 24 | | GK | | 4-0 | 26-15-11 | D04396 | | X2 | | TB0165C | C025 | 2 | | 115-199 |
| 0513 | 24 | | GK | | 3-0 | 26-15-11 | D04398 | | 2 | | TB0165A | A005 | 2 | | 001-099 |
| 0513 | 24 | | GK | | 2-0 | 26-15-11 | D04398 | | 2 | | TB0165C | A025 | 2 | | 115-199 |
| 0514 | 24 | | GK | | 8-0 | 26-15-11 | D41958J | | 24 | | TB0165A | C005 | 2 | | 001-099 |
| 0514 | 24 | | GK | | 7-0 | 26-15-11 | D41958J | | 24 | | TB0165C | C025 | 2 | | 115-199 |
| 0515 | 24 | | GK | | 7-0 | 26-15-11 | D41850J | | 15 | | D04394 | | A1 | | 001-099 |
| 0515 | 24 | | GK | | 10-0 | 26-15-11 | D04394 | | A1 | | D41850J | | 15 | | 115-199 |
| 0516 | 24 | | GK | | 3-0 | 26-15-11 | D04394 | | X2 | | TB0166Y | A020 | BJ | | 001-099 |
| 0516 | 24 | | GK | | 4-0 | 26-15-11 | D04394 | | X2 | | TB0165Y | A020 | BJ | | 115-199 |
| 0517 | 24 | | GK | | 3-0 | 26-15-11 | D04398 | | 4 | | TB0166Y | A020 | BJ | | 001-099 |
| 0517 | 24 | | GK | | 2-0 | 26-15-11 | D04398 | | 4 | | TB0165Y | A020 | BJ | | 115-199 |
| 0518 | 24 | | GK | | 3-0 | 26-15-11 | D04394 | | A2 | | GD01686 | DC.. | 2 | | 001-099 |
| 0518 | 22 | | GK | | 4-0 | 26-15-11 | D04394 | | A2 | | GD01686 | DC.. | 2 | | 115-199 |
| 0519 | 24 | | GK | | 8-0 | 26-15-11 | D04398 | | 3 | | D41958J | | 26 | | ALL |
| 0520 | 24 | | GK | | 7-0 | 26-15-11 | D04400 | | 2 | | D41850J | | 16 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 0520 | 24 | GK | | | 10-0 | 26-15-11 | D04400 | | 2 | | D41850J | | 16 | | 115-199 |
| 0521 | 24 | GK | | | 7-0 | 26-15-11 | D04400 | | 3 | | D41850J | | 14 | | 001-099 |
| 0521 | 24 | GK | | | 10-0 | 26-15-11 | D04400 | | 3 | | D41850J | | 14 | | 115-199 |
| 0522 | 24 | GK | | | 3-0 | 26-15-11 | D04396 | | X1 | | TB0166A | C011 | 2 | | 001-099 |
| 0522 | 24 | GK | | | 4-0 | 26-15-11 | D04396 | | X1 | | TB0165C | C021 | 2 | | 115-199 |
| 0523 | 24 | GK | | | 6-0 | 80-11-11 | D41938J | | 9 | | TB0168A | C003 | 2 | | 001-099 |
| 0523 | 24 | GK | | | 6-0 | 80-11-11 | D41938J | | 9 | | TB0166A | C015 | 2 | | 115-199 |
| 0524 | 24 | GK | | | 2-0 | 80-11-11 | TB0168A | A008 | 2 | | TB0168A | A003 | 2 | | 001-099 |
| 0524 | 24 | GK | | | 8-0 | 80-11-11 | TB0168A | A008 | 2 | | TB0166A | A015 | 2 | | 115-199 |
| 0525 | 24 | GK | | | 3-0 | 26-15-11 | D04398 | | 8 | | D04400 | | 1 | | 115-199 |
| 0526 | 24 | GK | | | 6-0 | 21-58-12 | D41060J | | 6 | | D05626 | C2 | | * | 001-099 |
| 0526 | 24 | GK | | | 8-0 | 21-58-12 | D41060J | | 6 | | D05626 | C2 | | * | 115-199 |
| 0529 | 22 | GK | | | 10-0 | 21-58-12 | D05190 | A3 | | * | D40056J | | 26 | | 001-099 |
| 0529 | 22 | GK | | | 9-0 | 21-58-12 | D05190 | A3 | | * | D40056J | | 26 | | 115-199 |
| 0578 | 20 | GK | | | 4-0 | 26-22-21 | D04400 | | 5 | | D04422 | X2 | | | ALL |
| 0579 | 20 | GK | | | 8-0 | 26-22-21 | D41060J | | 13 | | TB0166Z | 8 | BJ | | 115-199 |
| 0580 | 20 | GK | | | 8-0 | 26-22-21 | D40914J | | 5 | | TB0166Z | 8 | BJ | | 115-199 |
| 0581 | 20 | GK | | | 6-0 | 26-22-21 | D41948J | | 24 | | TB0166Z | 8 | BJ | | 115-199 |
| 0582 | 20 | GK | | | 1-0 | 26-22-21 | D04422 | | X1 | | D04422 | A2 | | * | 001-099 |
| 0582 | 20 | GK | | | 4-0 | 26-22-21 | D04422 | | X1 | | TB0166Z | 8 | BJ | | 115-199 |
| 0583 | 20 | GK | | | 7-0 | 26-22-21 | D04422 | | A1 | | D42096J | 6 | | | 001-099 |
| 0583 | 20 | GK | | | 4-0 | 26-22-21 | D04422 | | A2 | | TB0166Z | 8 | BJ | | 115-199 |
| 0584 | 20 | GK | | | 6-0 | 26-22-21 | D41948J | | 25 | | TB0166Z | 8 | BJ | | 115-199 |
| 0585 | 20 | GK | | | 7-0 | 26-22-21 | D41060J | | 12 | | TB0166Y | C014 | BJ | | 115-199 |
| 0586 | 20 | GK | | | 7-0 | 26-22-21 | D04422 | | A2 | * | D42096J | 11 | | | 001-099 |
| 0586 | 20 | GK | | | 4-0 | 26-22-21 | D04422 | | A1 | | TB0166Y | C014 | BJ | | 115-199 |
| 0587 | 20 | GK | | | 6-0 | 26-22-21 | D41948J | | 26 | | TB0166Y | C014 | BJ | | 115-199 |
| 0588 | 16 | GK | | | 6-0 | 29-21-31 | D03242 | | A2 | | D42096J | 16 | | | 001-099 |
| 0588 | 16 | GK | | | 6-0 | 29-21-31 | D03242 | | A2 | | SM00001 | | WI | | 115-199 |
| 0589 | 16 | GK | | | 1-6 | 29-21-31 | D03242 | | A1 | | SM00002 | | WI | | 001-099 |
| 0589 | 16 | GK | | | 1-0 | 29-21-31 | D03242 | | A1 | | SM00002 | | WI | | 115-199 |
| 0590 | 22 | GK | | | 7-0 | 29-21-31 | D03242 | | X1 | | D41958J | 55 | | | 001-099 |
| 0590 | 18 | GK | | | 8-0 | 29-21-31 | D03242 | | X1 | | D41958J | 55 | 18 | | 115-199 |
| 0591 | 20 | GK | | | 4-0 | 29-21-31 | D03242 | | X2 | | GD01685 | DC.. | 2 | | 001-099 |
| 0591 | 18 | GK | | | 4-0 | 29-21-31 | D03242 | | X2 | | GD01685 | DC.. | 2 | | 115-199 |
| 0592 | 24 | GK | | | 8-0 | 26-15-12 | D04396 | | B2 | | D41850J | 28 | | | 001-099 |
| 0592 | 24 | GK | | | 9-0 | 26-15-12 | D04396 | | B2 | | D41850J | 28 | | | 115-199 |
| 0593 | 24 | GK | | | 8-0 | 26-15-12 | D04396 | | A2 | | D41850J | 33 | | | 001-099 |
| 0593 | 24 | GK | | | 10-0 | 26-15-12 | D04396 | | A2 | | D41850J | 33 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0594 | 24 | | GK | | 8-0 | 26-15-12 | | D04396 | | A1 | | D41850J | 29 | | | 001-099 |
| 0594 | 24 | | GK | | 10-0 | 26-15-12 | | D04396 | | A1 | | D41850J | 29 | | | 115-199 |
| 0595 | 24 | | GK | | 8-0 | 26-15-12 | | D04396 | | B1 | | D41850J | 30 | | | 001-099 |
| 0595 | 24 | | GK | | 10-0 | 26-15-12 | | D04396 | | B1 | | D41850J | 30 | | | 115-199 |
| 0598 | 24 | | GK | | 8-0 | 26-15-11 | | D41850J | | 26 | | TB0166Y | A020 | BJ | | 001-099 |
| 0598 | 24 | | GK | | 10-0 | 26-15-12 | | D41850J | | 26 | | TB0165Y | A020 | BJ | | 115-199 |
| 0599 | 24 | | GK | | 9-0 | 24-51-71 | | D02992 | | A2 | | TB0168Y | C005 | BJ | | 001-099 |
| 0599 | 24 | | GK | | 8-0 | 24-51-71 | | D02992 | | A2 | | TB0168Y | C019 | BJ | | 115-199 |
| 0600 | 24 | | GK | | 2-0 | 24-51-71 | | D02992 | | A1 | | TB0166Y | C019 | BJ | | 001-099 |
| 0600 | 24 | | GK | | 4-0 | 24-51-71 | | D02992 | | A1 | | TB0165Y | C020 | BJ | | 115-199 |
| 0601 | 24 | | GK | | 8-0 | 24-51-71 | | D40608J | | 36 | | TB0166Y | C019 | BJ | | 001-099 |
| 0601 | 24 | | GK | | 8-0 | 24-51-71 | | D40608J | | 36 | | TB0165Y | C020 | BJ | | 115-199 |
| 0602 | 24 | | GK | | 8-0 | 24-51-71 | | D40608J | | 12 | | TB0166Y | C019 | BJ | | 001-099 |
| 0602 | 24 | | GK | | 8-0 | 24-51-71 | | D40608J | | 12 | | TB0165Y | C020 | BJ | | 115-199 |
| 0603 | 16 | | GK | | 9-0 | 75-31-11 | | D02700 | | A3 | | D41948J | 40 | 16 | | 001-099 |
| 0603 | 16 | | GK | | 8-0 | 75-31-11 | | D41948J | 40 | 16 | | D02700 | A3 | | | 115-199 |
| 0604 | 22 | | GK | | 8-0 | 31-31-32 | | D02994 | | 1 | | D41475J | 6 | | | 115-199 |
| 0605 | 22 | | GK | | 8-0 | 31-31-32 | | D02994 | | 2 | | TB0168Z | 5 | BJ | | 115-199 |
| 0606 | 22 | | GK | | 8-0 | 31-31-32 | | D02158 | | 5 | | TB0168Z | 5 | BJ | | 115-199 |
| 0607 | 22 | | GK | | 8-0 | 31-31-32 | | D02158 | | 2 | | D41475J | 7 | | | 115-199 |
| 0608 | 24 | | GK | | 8-0 | 26-15-11 | | D04398 | | 6 | | D41958J | 27 | | | 115-199 |
| 0609 | 24 | | GK | | 8-0 | 26-15-11 | | D04400 | | 6 | | D41958J | 28 | | | 115-199 |
| 0610 | 22 | | GK | | 8-0 | 31-31-32 | | D02702 | | 11 | | D41475J | 8 | | | 115-199 |
| 0611 | 22 | | GK | | 9-0 | 31-31-32 | | D02702 | | 10 | | TB0168Z | 5 | BJ | | 115-199 |
| 0616 | 22 | | GK | | 8-0 | 31-31-13 | | D41497J | | 29 | | TB0168Z | 5 | BJ | | 115-199 |
| 0619 | 18 | | GK | | 4-0 | 30-34-21 | | D04312 | | C2 | | TB0160G | 7 | 2 | | 001-099 |
| 0619 | 18 | | GK | | 4-0 | 30-34-21 | | D04312 | | C2 | | TB0161G | 6 | 2 | | 115-199 |
| 0621 | 24 | | GK | | 8-0 | 24-34-11 | | D04354 | | 13 | | D41497J | 27 | | | 001-099 |
| 0621 | 24 | | GK | | 9-0 | 24-34-11 | | D04354 | | 13 | | D41497J | 27 | | | 115-199 |
| 0622 | 24 | | GK | | 8-0 | 24-34-11 | | D04354 | | 1 | | D41850J | 46 | | | 001-099 |
| 0622 | 24 | | GK | | 9-0 | 24-34-11 | | D04354 | | 1 | | D41850J | 46 | | | 115-199 |
| 0630 | 20 | | GK | | 10-0 | 36-11-11 | | D07036 | | X1 | | D41022J | 40 | | | 001-009 |
| 0630 | 20 | | GK | | 5-0 | 36-11-11 | | D07036 | | X1 | | D41022J | 40 | | | 010-099 |
| 0630 | 20 | | GK | | 6-0 | 36-11-11 | | D07036 | | X1 | | D41022J | 40 | | | 115-199 |
| 0632 | 18 | | GK | | 4-0 | 30-34-21 | | D04312 | | C1 | | TB0160G | 8 | 2 | | 001-099 |
| 0632 | 18 | | GK | | 4-0 | 30-34-21 | | D04312 | | C1 | | TB0161G | 5 | 2 | | 115-199 |
| 0633 | 22 | | GK | | 1-0 | 78-34-11 | | D02746 | | A2 | | D02746 | X1 | | * | 001-099 |
| 0646 | 22 | | GK | | 8-0 | 76-11-11 | | D02154 | | 1 | | D41948J | 1 | | | 001-099 |
| 0647 | 20 | | GK | | 8-0 | 74-31-11 | | TB0166Y | A004 | BJ | | D41850J | 21 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|------|--|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | |
| 0647 | 20 | | GK | 8-0 | 74-31-11 | TB0165Y | A008 | BJ | | D41850J | 21 | | | 115-199 | |
| 0648 | 20 | | GK | 8-0 | 74-31-11 | TB0166Y | A018 | BJ | | D41850J | 27 | | | 001-099 | |
| 0648 | 20 | | GK | 8-0 | 74-31-11 | TB0165Y | C012 | BJ | | D41850J | 27 | | | 115-199 | |
| 0649 | 20 | | GK | 8-0 | 74-31-11 | TB0166Y | C004 | BJ | | D41060J | 39 | | | 001-099 | |
| 0649 | 20 | | GK | 8-0 | 74-31-11 | TB0165Y | C008 | BJ | | D41060J | 39 | | | 115-199 | |
| 0650 | 20 | | GK | 8-0 | 74-31-11 | TB0166Y | C018 | BJ | | D41060J | 33 | | | 001-099 | |
| 0650 | 20 | | GK | 8-0 | 74-31-11 | TB0165Y | C013 | BJ | | D41060J | 33 | | | 115-199 | |
| 0651 | 20 | | GK | 8-0 | 74-31-11 | TB0166Y | A004 | BJ | | D41938J | 10 | | | 001-099 | |
| 0651 | 20 | | GK | 7-0 | 74-31-11 | TB0165Y | A008 | BJ | | D41938J | 10 | | | 115-199 | |
| 0652 | 20 | | GK | 8-0 | 74-31-11 | TB0166Y | C004 | BJ | | D41958J | 12 | | | 001-099 | |
| 0652 | 20 | | GK | 8-0 | 74-31-11 | TB0165Y | C008 | BJ | | D41958J | 12 | | | 115-199 | |
| 0653 | 24 | | GK | 9-0 | 76-11-11 | D02154 | | 5 | | D41948J | 17 | | | 001-099 | |
| 0664 | 24 | | GK | 4-0 | 21-58-12 | D05618 | | 4 | | TB0160A | A017 | 2 | * | 001-099 | |
| 0664 | 24 | | GK | 5-0 | 21-58-12 | D05618 | | 4 | | TB0161A | A028 | 2 | * | 115-199 | |
| 0666 | 24 | | GK | 7-0 | 21-58-12 | D40056J | | 23 | | TB0166A | C029 | 2 | | 001-099 | |
| 0666 | 24 | | GK | 8-0 | 21-58-12 | D40056J | | 23 | | TB0166A | C029 | 2 | | 115-199 | |
| 0667 | 24 | | GK | 4-0 | 21-58-12 | D05622 | | 3 | | TB0166A | A026 | 2 | | ALL | |
| 0668 | 24 | | GK | 2-0 | 21-58-12 | D05622 | | 6 | | GD01684 | DC.. | 2 | | 001-099 | |
| 0668 | 24 | | GK | 4-0 | 21-58-12 | D05622 | | 6 | | GD01684 | DC.. | 2 | | 115-199 | |
| 0670 | 24 | | GK | 4-0 | 21-58-12 | D05622 | | 1 | | TB0166A | C028 | 2 | * | ALL | |
| 0673 | 24 | | GK | 7-0 | 21-58-12 | D41948J | | 45 | | TB0160A | C004 | 2 | | 001-099 | |
| 0673 | 24 | | GK | 8-0 | 21-58-12 | D41948J | | 45 | | TB0160A | C004 | 2 | | 115-199 | |
| 0679 | 24 | | GK | 5-0 | 21-58-13 | D05616 | | D2 | | K00343 | 13 | C | | 001-099 | |
| 0679 | 24 | | GK | 6-0 | 21-58-13 | D05616 | | D2 | | K00343 | 13 | C | | 115-199 | |
| 0681 | 22 | | GK | 2-0 | 21-58-24 | D05616 | | B2 | | GD01693 | AC.. | 2 | | 115-199 | |
| 0682 | 16 | | GK | 2-0 | 21-58-13 | D05616 | | C2 | | GD01693 | AC.. | 2 | | ALL | |
| 0683 | 22 | | GK | 9-0 | 21-58-24 | D05616 | | A2 | | D41020J | 47 | | | 115-199 | |
| 0686 | 22 | | GK | 4-0 | 21-58-24 | D05616 | | B3 | | D41022J | 2 | | | 115-199 | |
| 0688 | 24 | | GK | 5-0 | 21-58-12 | D05616 | | X1 | | M10689 | A | C | * | 001-099 | |
| 0688 | 24 | | GK | 9-0 | 21-58-12 | D05616 | | X1 | | M10689 | A | C | * | 115-199 | |
| 0698 | 24 | | GK | 6-0 | 21-58-12 | D05616 | | X2 | | D41060J | 32 | | | 001-099 | |
| 0698 | 24 | | GK | 10-0 | 21-58-12 | D05616 | | X2 | | D41060J | 32 | | | 115-199 | |
| 0700 | 20 | | GK | 7-0 | 36-11-11 | D07036 | | X2 | | GD01690 | DC.. | 2 | | 001-099 | |
| 0700 | 20 | | GK | 5-0 | 36-11-11 | D07036 | | X2 | | GD01690 | DC.. | 2 | | 115-199 | |
| 0703 | 24 | | GK | 4-0 | 21-58-12 | D05622 | | 7 | | TB0166A | C026 | 2 | | ALL | |
| 0704 | 24 | | GK | 4-0 | 21-58-12 | D41948J | | 41 | | SM00012 | | WI | | ALL | |
| 0708 | 20 | | GK | 9-0 | 36-11-11 | D07036 | | B3 | | D40874J | 29 | | | 001-099 | |
| 0708 | 20 | | GK | 7-0 | 36-11-11 | D07036 | | B3 | | D40874J | 29 | | | 115-199 | |
| 0710 | 24 | | GK | 7-0 | 21-58-11 | TB0161A | | C003 | 2 | SM00010 | | WI | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0736 | 20 | | GK | | 9-0 | 29-11-22 | | D05662 | | A1 | | M00500 | A | C | | 001-099 |
| 0736 | 20 | | GK | | 8-0 | 29-11-22 | | D05662 | | A1 | | TB0168X | B017 | BJ | | 115-199 |
| 0737 | 20 | | GK | | 8-0 | 29-11-22 | | D05662 | | X1 | | D40910J | 32 | | | 001-099 |
| 0737 | 20 | | GK | | 8-0 | 29-11-22 | | D05662 | | X1 | | D40910J | 14 | | | 115-199 |
| 0738 | 20 | | GK | | 4-0 | 29-11-22 | | D05662 | | X2 | | GD01685 | AC.. | 2 | | ALL |
| 0739 | 22 | | GK | | 8-0 | 29-11-31 | | D05664 | | X1 | | D40910J | 17 | | | 001-099 |
| 0739 | 22 | | GK | | 9-0 | 29-11-31 | | D05664 | | X1 | | D40910J | 17 | | | 115-199 |
| 0740 | 20 | | GK | | 4-0 | 29-11-31 | | D05664 | | X2 | | GD01685 | AC.. | 2 | | ALL |
| 0741 | 22 | | GK | | 9-0 | 29-11-31 | | D05664 | | A1 | | M10482 | A | C | | 001-099 |
| 0741 | 22 | | GK | | 8-0 | 29-11-31 | | D05664 | | A1 | | TB0168X | B009 | BJ | | 115-199 |
| 0742 | 22 | | GK | | 3-0 | 29-11-31 | | D05664 | | A2 | | D04726 | X2 | | * | 001-099 |
| 0742 | 22 | | GK | | 8-0 | 29-11-31 | | D05664 | | A2 | | TB0168Y | A003 | BJ | | 115-199 |
| 0744 | 22 | | GK | | 9-0 | 29-11-31 | | D05654 | | A1 | | M10020 | A | C | | 001-099 |
| 0744 | 22 | | GK | | 8-0 | 29-11-31 | | D05654 | | A1 | | TB0168X | C017 | BJ | | 115-199 |
| 0746 | 22 | | GK | | 8-0 | 29-11-31 | | D05654 | | X1 | | D40914J | 3 | | | 001-099 |
| 0746 | 22 | | GK | | 9-0 | 29-11-31 | | D05654 | | X1 | | D40914J | 3 | | | 115-199 |
| 0747 | 20 | | GK | | 4-0 | 29-11-31 | | D05654 | | X2 | | GD01685 | AC.. | 2 | | ALL |
| 0783 | 22 | | GK | | 2-0 | 30-32-11 | | D40582J | | 25 | | D41473J | 18 | | | 001-099 |
| 0783 | 22 | | GK | | 3-0 | 30-32-11 | | D40582J | | 25 | | D41473J | 18 | | | 115-199 |
| 0784 | 22 | | GK | | 10-0 | 29-22-11 | | D04704 | | C1 | | D41024J | 13 | | | 001-099 |
| 0784 | 22 | | GK | | 12-0 | 29-22-11 | | D04704 | | C1 | | D41850J | 31 | | | 115-199 |
| 0785 | 22 | | GK | | 4-0 | 29-22-11 | | D04704 | | C2 | | GD01671 | DC.. | 2 | | ALL |
| 0786 | 22 | | GK | | 10-0 | 29-22-11 | | D04704 | | D2 | | D41024J | 14 | | | 001-099 |
| 0786 | 22 | | GK | | 10-0 | 29-22-11 | | D04704 | | D2 | | D41850J | 34 | | | 115-199 |
| 0787 | 22 | | GK | | 9-0 | 29-22-11 | | D04704 | | D3 | | D41948J | 42 | | | 001-099 |
| 0787 | 22 | | GK | | 10-0 | 29-22-11 | | D04704 | | D3 | | D41850J | 35 | | | 115-199 |
| 0788 | 22 | | GK | | 6-0 | 32-09-11 | | D41612J | | 9 | | D02754 | 10 | | | ALL |
| 0789 | 22 | | GK | | 3-0 | 32-09-11 | | D02754 | | 11 | | GD01671 | DC.. | 2 | | 001-099 |
| 0789 | 22 | | GK | | 4-0 | 32-09-11 | | D02754 | | 11 | | GD01671 | DC.. | 2 | | 115-199 |
| 0791 | 24 | | GK | | 4-0 | 21-58-11 | | TB0161A | | A003 | 2 | GD01674 | DC.. | 2 | | 001-099 |
| 0791 | 24 | | GK | | 3-0 | 21-58-11 | | TB0161A | | A003 | 2 | GD01674 | DC.. | 2 | | 115-199 |
| 0797 | 22 | | GK | | 10-0 | 32-61-21 | | D04354 | | 3 | | D41958J | 31 | | | 001-099 |
| 0797 | 22 | | GK | | 8-0 | 32-61-21 | | D41958J | | 31 | | D04354 | 3 | | | 115-199 |
| 0798 | 24 | | GK | | 10-0 | 73-21-12 | | D07004 | | C1 | * | D07002 | X1 | | * | 001-099 |
| 0798 | 24 | | GK | | 8-0 | 73-21-12 | | D07004 | | C1 | * | D07002 | X1 | | * | 115-199 |
| 0799 | 24 | | GK | | 3-0 | 73-21-12 | | D07002 | | X2 | | GD01683 | DC.. | 2 | | 001-099 |
| 0799 | 24 | | GK | | 4-0 | 73-21-12 | | D07002 | | X2 | | GD01683 | DC.. | 2 | | 115-199 |
| 0800 | 20 | | GK | | 12-0 | 73-21-12 | | D07002 | | A1 | * | D41948J | 43 | | | 001-099 |
| 0800 | 20 | | GK | | 8-0 | 73-21-12 | | D07002 | | A1 | * | D41948J | 42 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0801 | 20 | | GK | | 3-0 | 73-21-12 | D07002 | | A2 | | GD01683 | DC.. | 2 | | 001-099 |
| 0801 | 20 | | GK | | 4-0 | 73-21-12 | D07002 | | A2 | | GD01683 | DC.. | 2 | | 115-199 |
| 0802 | 24 | | GK | | 11-0 | 73-21-12 | D07004 | | X1 | | D41475J | 48 | | | 001-099 |
| 0802 | 24 | | GK | | 7-0 | 73-21-12 | D07004 | | X1 | | D41475J | 48 | | | 115-199 |
| 0803 | 24 | | GK | | 4-0 | 73-21-12 | D07004 | | X2 | | GD02867 | DC.. | 2 | | 001-099 |
| 0803 | 24 | | GK | | 3-0 | 73-21-12 | D07004 | | X2 | | GD02867 | DC.. | 2 | | 115-199 |
| 0804 | 20 | | GK | | 11-0 | 73-21-12 | D07004 | | A2 | | D07002 | A1 | | * | 001-099 |
| 0804 | 20 | | GK | | 8-0 | 73-21-12 | D07004 | | A2 | | D07002 | A1 | | * | 115-199 |
| 0805 | 20 | | GK | | 4-0 | 73-21-12 | D07004 | | A3 | | GD02867 | DC.. | 2 | | 001-099 |
| 0805 | 20 | | GK | | 3-0 | 73-21-12 | D07004 | | A3 | | GD02867 | DC.. | 2 | | 115-199 |
| 0806 | 24 | | GK | | 10-0 | 73-21-12 | D07004 | | C1 | * | D41948J | 37 | | | 001-099 |
| 0806 | 24 | | GK | | 7-0 | 73-21-12 | D07004 | | C1 | * | D41948J | 37 | | | 115-199 |
| 0808 | 22 | | GK | | 4-0 | 33-16-11 | D02596 | | B2 | | GD01683 | DC.. | 2 | | ALL |
| 0812 | 24 | | GK | | 7-0 | 27-32-11 | D41473J | | 6 | | TB0160Y | C005 | BJ | | 001-099 |
| 0812 | 24 | | GK | | 6-0 | 27-32-11 | D41473J | | 6 | | TB0160Y | A026 | BJ | | 115-199 |
| 0814 | 24 | | GK | | 4-0 | 27-32-11 | D00602 | | 9 | | TB0160Y | C005 | BJ | | 001-099 |
| 0814 | 24 | | GK | | 3-0 | 27-32-11 | D00602 | | 9 | | TB0160Y | A026 | BJ | | 115-199 |
| 0815 | 24 | | GK | | 4-0 | 27-32-11 | D00602 | | 11 | | GD01674 | DC.. | 2 | | ALL |
| 0817 | 24 | | GK | | 4-0 | 31-51-41 | D01780 | | 1 | | D00600 | 8 | | | 001-099 |
| 0817 | 24 | | GK | | 3-0 | 31-51-41 | D01780 | | 1 | | D00600 | 8 | | | 115-199 |
| 0818 | 20 | | GK | | 10-0 | 74-31-11 | D07028 | | X2 | | D41938J | 20 | | | 001-099 |
| 0818 | 20 | | GK | | 8-0 | 74-31-11 | D07028 | | X2 | | D41938J | 20 | | | 115-199 |
| 0820 | 20 | | GK | | 3-0 | 74-31-11 | D07028 | | X1 | | TB0166Z | 7 | BJ | | 001-099 |
| 0820 | 20 | | GK | | 4-0 | 74-31-11 | D07028 | | X1 | | TB0166Z | 7 | BJ | | 115-199 |
| 0821 | 20 | | GK | | 10-0 | 74-31-11 | D07028 | | A1 | | D41938J | 22 | | | 001-099 |
| 0821 | 20 | | GK | | 4-0 | 74-31-11 | D07028 | | A1 | | TB0165Y | A003 | BJ | | 115-199 |
| 0822 | 20 | | GK | | 10-0 | 74-31-11 | D07028 | | A2 | | D41938J | 21 | | | 001-099 |
| 0822 | 20 | | GK | | 8-0 | 74-31-11 | D07028 | | A2 | | D41938J | 21 | | | 115-199 |
| 0823 | 20 | | GK | | 10-0 | 74-31-11 | D07028 | | B1 | | D41958J | 39 | | | 001-099 |
| 0823 | 20 | | GK | | 4-0 | 74-31-11 | D07028 | | B1 | | TB0165Y | C003 | BJ | | 115-199 |
| 0824 | 20 | | GK | | 10-0 | 74-31-11 | D07028 | | B2 | | D41958J | 37 | | | 001-099 |
| 0824 | 20 | | GK | | 8-0 | 74-31-11 | D07028 | | B2 | | D41958J | 37 | | | 115-199 |
| 0825 | 20 | | GK | | 4-0 | 74-31-11 | D02520 | | A3 | | TB0165Y | A003 | BJ | | 115-199 |
| 0826 | 20 | | GK | | 4-0 | 74-31-11 | D02522 | | A3 | | TB0165Y | C003 | BJ | | 115-199 |
| 0835 | 24 | | GK | | 3-0 | 21-58-12 | D01572 | | 5 | | TB0160A | A017 | 2 | * | 001-099 |
| 0835 | 24 | | GK | | 3-0 | 21-58-12 | D01572 | | 5 | | TB0161A | A028 | 2 | | 115-199 |
| 0837 | 24 | | GK | | 3-0 | 21-58-12 | D01572 | | 2 | | GD01673 | DC.. | 2 | | ALL |
| 0838 | 20 | | GK | | 9-0 | 36-11-11 | D07036 | | C1 | * | D04116 | 7 | | | 001-099 |
| 0838 | 20 | | GK | | 7-0 | 36-11-11 | D07036 | | C1 | | TB0165Y | C002 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 22

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | | |
| 0839 | 20 | | GK | | 2-0 | 36-11-11 | D04116 | | 7 | | | TB0165Y | C002 | BJ | | 115-199 | |
| 0840 | 20 | | GK | | 9-0 | 36-11-11 | D07046 | | 9 | | | D07036 | B2 | | | 001-099 | |
| 0840 | 20 | | GK | | 7-0 | 36-11-11 | D07036 | | B2 | | | D07046 | 9 | | | 115-199 | |
| 0841 | 22 | | GK | | 3-0 | 77-12-41 | D07046 | | 6 | | | TB0160Y | C020 | BJ | | 001-099 | |
| 0841 | 22 | | GK | | 4-0 | 77-12-41 | D07046 | | 6 | | | D04704 | X1 | | * | 115-199 | |
| 0842 | 22 | | GK | | 3-0 | 77-12-41 | D07046 | | 12 | | | GD01672 | DC.. | 2 | | 001-099 | |
| 0842 | 22 | | GK | | 4-0 | 77-12-41 | D07046 | | 12 | | | GD01672 | DC.. | 2 | | 115-199 | |
| 0845 | 20 | | GK | | 8-0 | 32-35-11 | D04354 | | 8 | | | D41958J | 34 | | | 115-199 | |
| 0847 | 20 | | GK | | 4-0 | 32-35-11 | D04354 | | 7 | | | GD01686 | DC.. | 2 | | 115-199 | |
| 0853 | 20 | | GK | | 3-0 | 32-35-11 | K10369 | | X2 | C | | TB0360A | C013 | 2 | | 001-099 | |
| 0853 | 20 | | GK | | 2-0 | 32-35-11 | K10369 | | X2 | C | | TB0360A | C013 | 2 | | 115-199 | |
| 0854 | 20 | | GK | | 3-0 | 32-35-11 | K10369 | | X1 | C | | TB0360A | C014 | 2 | | 001-099 | |
| 0854 | 20 | | GK | | 2-0 | 32-35-11 | K10369 | | X1 | C | | TB0360A | C014 | 2 | | 115-199 | |
| 0855 | 20 | | GK | | 1-0 | 32-35-11 | TB0360A | A013 | 2 | | | TB0360A | A014 | 2 | | ALL | |
| 0859 | 22 | | GK | | 9-0 | 21-58-15 | D07078 | | A2 | | | D40910J | 22 | | | 001-099 | |
| 0859 | 22 | | GK | | 7-0 | 21-58-15 | D07078 | | A2 | | | D40910J | 22 | | | 115-199 | |
| 0860 | 22 | | GK | | 9-0 | 21-58-15 | D07078 | | B2 | | | D40910J | 23 | | | 001-099 | |
| 0860 | 22 | | GK | | 7-0 | 21-58-15 | D07078 | | B2 | | | D40910J | 23 | | | 115-199 | |
| 0861 | 22 | | GK | | 9-0 | 21-58-15 | D07078 | | C2 | | | D40910J | 24 | | | 001-099 | |
| 0861 | 22 | | GK | | 7-0 | 21-58-15 | D07078 | | C2 | | | D40910J | 24 | | | 115-199 | |
| 0862 | 22 | | GK | | 8-0 | 21-58-15 | D07078 | | A3 | | | D40056J | 29 | | | 001-099 | |
| 0862 | 22 | | GK | | 7-0 | 21-58-15 | D07078 | | A3 | | | D40056J | 29 | | | 115-199 | |
| 0863 | 22 | | GK | | 8-0 | 21-58-15 | D07078 | | B3 | | | D40056J | 30 | | | 001-099 | |
| 0863 | 22 | | GK | | 7-0 | 21-58-15 | D07078 | | B3 | | | D40056J | 30 | | | 115-199 | |
| 0865 | 22 | | GK | | 8-0 | 21-58-15 | D07078 | | C3 | | | D40056J | 31 | | | 001-099 | |
| 0865 | 22 | | GK | | 7-0 | 21-58-15 | D07078 | | C3 | | | D40056J | 31 | | | 115-199 | |
| 0866 | 22 | | GK | | 9-0 | 21-58-15 | D07078 | | X1 | | | D40292J | 7 | | | 001-002 | |
| 0866 | 22 | | GK | | 9-0 | 21-58-15 | D07078 | | X1 | | | TB0161Y | A018 | BJ | | 003-099 | |
| 0866 | 22 | | GK | | 7-0 | 21-58-15 | D07078 | | X1 | | | D40292J | 7 | | | 115-199 | |
| 0867 | 22 | | GK | | 10-0 | 21-58-15 | D07078 | | X2 | | | TB0161Y | A024 | BJ | | 001-099 | |
| 0867 | 22 | | GK | | 7-0 | 21-58-15 | D07078 | | X2 | | | TB0161Y | A024 | BJ | | 115-199 | |
| 0869 | 22 | | GK | | 8-0 | 21-58-15 | D41060J | | 9 | | | TB0161Y | A024 | BJ | | ALL | |
| 0870 | 22 | | GK | | 8-0 | 21-58-15 | D41024J | | 17 | | | TB0161Y | A024 | BJ | | 001-099 | |
| 0870 | 22 | | GK | | 8-0 | 21-58-15 | D41024J | | 8 | | | TB0161Y | A024 | BJ | | 115-199 | |
| 0871 | 24 | | GK | | 2-0 | 24-25-13 | D41475J | | 46 | | | D40292J | 3 | | | 001-002, 115-199 | |
| 0872 | 24 | | GK | | 2-0 | 24-25-13 | D41475J | | 47 | | | D40292J | 4 | | | ALL | |
| 0873 | 24 | | GK | | 2-0 | 24-25-13 | D41475J | | 49 | | | D40292J | 5 | | | ALL | |
| 0874 | 24 | | GK | | 2-0 | 24-25-13 | D41475J | | 44 | | | D40292J | 6 | | | ALL | |
| 0875 | 22 | | GK | | 9-0 | 24-25-11 | D04182 | | A1 | | | D40292J | 1 | | | 001-002 | |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 23

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 0875 | 22 | GK | | | 8-0 | 24-25-11 | D04182 | A1 | | | D40292J | 1 | | | 115-199 |
| 0876 | 22 | GK | | | 9-0 | 24-25-11 | D04182 | A2 | * | | D40914J | 6 | | | 001-099 |
| 0876 | 22 | GK | | | 7-0 | 24-25-11 | D04182 | A2 | * | | D40914J | 6 | | | 115-199 |
| 0877 | 22 | GK | | | 1-0 | 24-25-11 | D04182 | A2 | * | | D04182 | X1 | * | | 001-002, 115-199 |
| 0877 | 22 | GK | | | 8-0 | 24-25-11 | D04182 | A2 | * | | D40292J | 1 | | | 003-099 |
| 0878 | 22 | GK | | | 9-0 | 24-25-11 | D04182 | X1 | * | | D40292J | 2 | | | 001-002 |
| 0878 | 22 | GK | | | 8-0 | 24-25-11 | D04182 | A3 | | | D40292J | 2 | | | 003-099 |
| 0878 | 22 | GK | | | 8-0 | 24-25-11 | D04182 | X1 | * | | D40292J | 2 | | | 115-199 |
| 0879 | 22 | GK | | | 10-0 | 24-25-11 | D04182 | X2 | * | | D41850J | 32 | | | 001-002 |
| 0879 | 22 | GK | | | 8-0 | 24-25-11 | D04182 | X2 | * | | D41850J | 32 | | | 115-199 |
| 0882 | 22 | GK | | | 8-0 | 32-09-11 | D41612J | 24 | | | TB0160A | C003 | 2 | | 001-002 |
| 0882 | 22 | GK | | | 8-0 | 32-09-11 | D41612J | 24 | | | TB0160A | C024 | 2 | | 003-099 |
| 0885 | 22 | GK | | | 7-0 | 36-11-11 | TB0166Z | 12 | BJ | | D41022J | 9 | | | 001-099 |
| 0885 | 22 | GK | | | 8-0 | 36-11-11 | D41022J | 9 | | | TB0166Z | 16 | BJ | | 115-199 |
| 0886 | 24 | GK | | | 8-0 | 21-25-11 | D05501 | 7 | | | D41020J | 43 | | | 001-099 |
| 0886 | 24 | GK | | | 7-0 | 21-25-11 | D05501 | 7 | | | D41020J | 43 | | | 115-199 |
| 0887 | 24 | GK | | | 3-0 | 21-25-11 | D05192 | 3 | | | TB0165A | A001 | 2 | | 001-099 |
| 0887 | 24 | GK | | | 5-0 | 21-25-11 | D05192 | 3 | | | TB0165A | A001 | 2 | | 115-199 |
| 0888 | 24 | GK | | | 10-0 | 21-25-11 | D05192 | 4 | | | D41020J | 41 | | | 001-099 |
| 0888 | 24 | GK | | | 8-0 | 21-25-11 | D05192 | 4 | | | D41020J | 41 | | | 115-199 |
| 0889 | 24 | GK | | | 3-0 | 21-25-11 | D05192 | 7 | | | TB0165A | C001 | 2 | | 001-099 |
| 0889 | 24 | GK | | | 5-0 | 21-25-11 | D05192 | 7 | | | TB0165A | C001 | 2 | | 115-199 |
| 0890 | 24 | GK | | | 7-0 | 21-25-11 | D40056J | 22 | | | TB0160Y | C026 | BJ | | 001-099 |
| 0890 | 24 | GK | | | 8-0 | 21-25-11 | D40056J | 22 | | | TB0160Y | C026 | BJ | | 115-199 |
| 0891 | 24 | GK | | | 4-0 | 21-25-11 | D00582 | 1 | | | TB0160Y | C026 | BJ | | 001-099 |
| 0891 | 24 | GK | | | 3-0 | 21-25-11 | D00582 | 1 | | | TB0160Y | C026 | BJ | | 115-199 |
| 0892 | 24 | GK | | | 7-0 | 21-25-11 | D40716J | 1 | | | TB0165A | C001 | 2 | | 001-099 |
| 0892 | 24 | GK | | | 8-0 | 21-25-11 | D40716J | 1 | | | TB0165A | C001 | 2 | | 115-199 |
| 0893 | 24 | GK | | | 11-0 | 21-25-11 | D05622 | 4 | | | TB0160Y | A027 | BJ | | 001-099 |
| 0893 | 24 | GK | | | 10-0 | 21-25-11 | D05622 | 4 | | | TB0160Y | A027 | BJ | | 115-199 |
| 0894 | 24 | GK | | | 8-0 | 21-25-11 | D40910J | 3 | | | TB0160Y | A027 | BJ | | ALL |
| 0896 | 24 | GK | | | 6-0 | 21-25-11 | D05626 | B2 | | | D41020J | 7 | | | ALL |
| 0897 | 24 | GK | | | 6-0 | 21-25-11 | D05626 | B3 | | | D40608J | 28 | | | ALL |
| 0898 | 24 | GK | | | 8-0 | 21-58-12 | D00600 | 13 | | | D41060J | 7 | | | 001-099 |
| 0898 | 24 | GK | | | 7-0 | 21-58-12 | D00600 | 13 | | | D41060J | 7 | | | 115-199 |
| 0899 | 24 | GK | | | 12-0 | 21-58-12 | D00600 | 1 | | | D05190 | B1 | | | 001-099 |
| 0899 | 24 | GK | | | 10-0 | 21-58-12 | D00600 | 1 | | | D05190 | B1 | | | 115-199 |
| 0900 | 22 | GK | | | 10-0 | 21-58-12 | D41060J | 31 | | | D02596 | A2 | | | 001-099 |
| 0900 | 22 | GK | | | 8-0 | 21-58-12 | D41060J | 31 | | | D02596 | A2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 24

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0901 | 22 | | GK | | 7-0 | 21-58-15 | K00343 | 11 | C | | TB0161Y | A024 | BJ | | ALL |
| 0902 | 22 | | GK | | 2-0 | 21-58-15 | K00343 | 12 | C | | GD01606 | DC.. | F | | 001-099 |
| 0902 | 22 | | GK | | 1-0 | 21-58-15 | K00343 | 12 | C | | GD01606 | DC.. | F | | 115-199 |
| 0903 | 24 | | GK | | 5-0 | 21-58-12 | D05626 | C2 | | * | M10689 | A | C | * | 001-099 |
| 0903 | 24 | | GK | | 4-0 | 21-58-12 | D05626 | C2 | | * | M10689 | A | C | * | 115-199 |
| 0904 | 24 | | GK | | 8-0 | 21-58-12 | D41024J | 3 | | | TB0166A | C027 | 2 | | ALL |
| 0905 | 22 | | GK | | 2-0 | 21-58-12 | D02596 | A3 | | | D05190 | A1 | | * | 001-099 |
| 0905 | 22 | | GK | | 3-0 | 21-58-12 | D02596 | A3 | | | D05190 | A1 | | * | 115-199 |
| 0906 | 24 | | GK | | 2-0 | 21-58-12 | TB0166A | A026 | 2 | | TB0166A | A029 | 2 | | ALL |
| 0908 | 24 | | GK | | 7-0 | 21-58-12 | D41850J | 36 | | | M10690 | A | C | | 001-099 |
| 0908 | 24 | | GK | | 6-0 | 21-58-12 | D41850J | 36 | | | M10690 | A | C | | 115-199 |
| 0909 | 24 | | GK | | 6-0 | 21-58-12 | D41060J | 34 | | | M10690 | A | C | | 001-099 |
| 0909 | 24 | | GK | | 5-0 | 21-58-12 | D41060J | 34 | | | M10690 | A | C | | 115-199 |
| 0910 | 24 | | GK | | 10-0 | 21-58-12 | D41060J | 18 | | | TB0160Z | 22 | BJ | | 001-099 |
| 0910 | 24 | | GK | | 8-0 | 21-58-12 | D41060J | 18 | | | TB0160Z | 22 | BJ | | 115-199 |
| 0911 | 24 | | GK | | 10-0 | 21-58-12 | D41850J | 53 | | | TB0160Z | 22 | BJ | | 001-099 |
| 0911 | 24 | | GK | | 8-0 | 21-58-12 | D41850J | 53 | | | TB0160Z | 22 | BJ | | 115-199 |
| 0912 | 24 | | GK | | 3-0 | 21-58-12 | D40874J | 40 | | | SM00015 | | WI | | 001-099 |
| 0912 | 24 | | GK | | 4-0 | 21-58-12 | D40874J | 40 | | | SM00015 | | WI | | 115-199 |
| 0913 | 24 | | GK | | 8-0 | 21-58-12 | D40874J | 42 | | | TB0160Z | 22 | BJ | | 001-099 |
| 0913 | 24 | | GK | | 6-0 | 21-58-12 | D40874J | 42 | | | TB0160Z | 22 | BJ | | 115-199 |
| 0914 | 16 | | GK | | 4-0 | 21-58-12 | D00572 | C2 | | | GD01671 | DC.. | 2 | | ALL |
| 0916 | 24 | | GK | | 9-0 | 21-58-12 | D00572 | C1 | | | TB0166A | C028 | 2 | * | ALL |
| 0917 | 24 | | GK | | 6-0 | 21-58-12 | D04266 | B3 | | | D41948J | 46 | | | ALL |
| 0918 | 24 | | GK | | 5-0 | 21-58-12 | D04266 | B2 | | | SM00015 | | WI | | 001-099 |
| 0918 | 24 | | GK | | 4-0 | 21-58-12 | D04266 | B2 | | | SM00015 | | WI | | 115-199 |
| 0920 | 24 | | GK | | 1-0 | 21-58-12 | D04266 | A1 | | | D04266 | X2 | | * | 001-099 |
| 0920 | 24 | | GK | | 3-0 | 21-58-12 | D04266 | A1 | | | D04266 | X2 | | * | 115-199 |
| 0921 | 24 | | GK | | 5-0 | 21-58-12 | D04266 | X1 | | | M10691 | B | C | | 001-099 |
| 0921 | 24 | | GK | | 4-0 | 21-58-12 | D04266 | X1 | | | M10691 | B | C | | 115-199 |
| 0922 | 24 | | GK | | 8-0 | 21-58-12 | D04266 | X2 | | * | TB0161A | A025 | 2 | | 001-099 |
| 0922 | 24 | | GK | | 6-0 | 21-58-12 | D04266 | X2 | | * | TB0161A | A025 | 2 | | 115-199 |
| 0923 | 24 | | GK | | 5-0 | 21-58-12 | D05626 | D3 | | | M10690 | B | C | | ALL |
| 0924 | 24 | | GK | | 7-0 | 21-58-12 | D05626 | D2 | | | TB0166A | C028 | 2 | | 001-099 |
| 0924 | 24 | | GK | | 8-0 | 21-58-12 | D05626 | D2 | | | TB0166A | C028 | 2 | | 115-199 |
| 0926 | 24 | | GK | | 5-0 | 21-58-12 | D05626 | C3 | | | M10691 | A | C | | ALL |
| 0927 | 24 | | GK | | 5-0 | 21-58-12 | D05626 | C1 | | | M10691 | B | C | | ALL |
| 0928 | 24 | | GK | | 5-0 | 21-58-12 | D41022J | 12 | | | TB0163A | A004 | 2 | | ALL |
| 0930 | 24 | | GK | | 7-0 | 21-58-12 | TB0160A | A017 | 2 | | TB0163A | A004 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 25

Oct 09/2008



WIRE LIST

91-21-11

Section W1260

Page 26

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 0966 | 24 | | GK | | 8-0 | 21-58-24 | D04210 | | 13 | | D41020J | 48 | | | 115-199 |
| 0967 | 24 | | GK | | 4-0 | 21-58-24 | D04210 | | 12 | | TB0161A | C028 | 2 | | 115-199 |
| 0968 | 22 | | GK | | 4-0 | 34-22-16 | D40728J | | 12 | | D41497J | 4 | | | 001, 003-099 |
| 0968 | 22 | | GA | | 4-0 | 34-22-16 | D40728J | | 12 | | TB0163A | A011 | 2 | | 002 |
| 0968 | 20 | | GK | | 5-0 | 34-22-16 | D40728J | | 12 | | TB0163Y | A013 | BJ | | 115-199 |
| 0977 | 22 | | GK | | 3-0 | 32-09-11 | D00608 | | X2 | * | TB0160A | A028 | 2 | | 001-099 |
| 0980 | 22 | | GK | | 3-0 | 24-25-11 | D41024J | | 9 | | D40292J | 8 | | | 001-002 |
| 0980 | 22 | | GK | | 3-0 | 24-25-11 | D40292J | | 8 | | D41024J | 9 | | | 115-199 |
| 0981 | 22 | | GK | | 3-0 | 32-09-11 | TB0160A | C024 | 2 | | TB0160A | C003 | 2 | | 001-002 |
| 0981 | 22 | | GK | | 10-0 | 32-09-11 | TB0360B | C015 | 2 | | TB0160A | C003 | 2 | | 003-099 |
| 0981 | 22 | | GK | | 1-0 | 32-09-11 | TB0160A | C003 | 2 | | TB0160A | C015 | 2 | | 115-199 |
| 0983 | 24 | | GK | | 5-0 | 21-51-11 | D04790 | | 2 | | TB0165Y | A002 | BJ | | 001-099 |
| 0984 | 24 | | GK | | 11-0 | 21-51-11 | D04790 | | 3 | | D41544J | 1 | | | 001-099 |
| 0985 | 24 | | GK | | 11-0 | 21-51-11 | D04790 | | 5 | | D40728J | 9 | | | 001-099 |
| 0986 | 24 | | GK | | 5-0 | 21-51-11 | D04790 | | 7 | | TB0165Y | A002 | BJ | | 001-099 |
| 0988 | 22 | | GK | | 8-0 | 49-61-11 | D42080J | | 15 | | TB0165Y | A002 | BJ | | 001-099 |
| 0989 | 24 | | GK | | 3-0 | 21-51-12 | D02950 | | X1 | * | D02948 | X1 | | * | 001-099 |
| 0990 | 24 | | GK | | 11-0 | 21-51-12 | D02948 | | A1 | | D41544J | 7 | | | 001-099 |
| 0991 | 24 | | GK | | 11-0 | 21-51-12 | D02948 | | B1 | | D41544J | 6 | | | 001-099 |
| 0992 | 24 | | GK | | 11-0 | 21-51-12 | D02948 | | C1 | | D41544J | 5 | | | 001-099 |
| 0993 | 24 | | GK | | 12-0 | 21-51-12 | D02950 | | X1 | * | D04052 | 6 | | | 001-099 |
| 0994 | 24 | | GK | | 3-0 | 21-51-12 | D02950 | | X2 | * | D02948 | X2 | | * | 001-099 |
| 0995 | 24 | | GK | | 10-0 | 21-51-12 | D02950 | | A1 | | D41544J | 4 | | | 001-099 |
| 0996 | 24 | | GK | | 10-0 | 21-51-12 | D02950 | | B1 | | D41544J | 3 | | | 001-099 |
| 0997 | 24 | | GK | | 10-0 | 21-51-12 | D02950 | | C1 | | D41544J | 20 | | | 001-099 |
| 0998 | 24 | | GK | | 12-0 | 21-51-12 | D02950 | | X2 | * | D04052 | 12 | | | 001-099 |
| 1122 | 20 | | GE | CL | 3-0 | 78-34-51 | D07776 | | A1 | | D01782 | 11 | | | 001-099 |
| 1122 | 20 | | GE | CL | 3-0 | 78-34-51 | D01782 | | 11 | | D07776 | A1 | | | 115-199 |
| 1122Z | | | | CL | 0-0 | 78-34-51 | D07776 | | | AE | D01782 | DED | | | 001-099 |
| 1122Z | | | | CL | 0-0 | 78-34-51 | D01782 | | DED | | D07776 | | | AE | 115-199 |
| 1123 | 20 | | GE | CM | 3-0 | 78-34-51 | D07776 | | A3 | | GD01672 | ST.. | 2 | | 001-099 |
| 1123 | 20 | | GE | CM | 4-0 | 78-34-51 | D07776 | | A3 | | GD01672 | ST.. | 2 | | 115-199 |
| 1123Z | | | | CM | 0-0 | 78-34-51 | D07776 | | | AE | GD01672 | ST.. | 2 | | ALL |
| 1124 | 20 | | GE | CN | 3-0 | 78-34-51 | D07776 | | X1 | | D41948J | 50 | | | 001-002 |
| 1124 | 20 | | GE | CN | 9-0 | 78-34-51 | D07776 | | X1 | | D41948J | 7 | | | 003-099 |
| 1124 | 20 | | GE | CN | 7-0 | 78-34-51 | D07776 | | X1 | | D41948J | 50 | | | 115-199 |
| 1124Z | | | | CN | 0-0 | 78-34-51 | D07776 | | | AE | D41948J | 49 | | | ALL |
| 1125 | 18 | | GE | CK | 3-0 | 78-34-51 | D07776 | | A2 | | TB0161C | C029 | 2 | | ALL |
| 1125Z | | | | CK | 0-0 | 78-34-51 | D07776 | | DED | | TB0161C | | | AD | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 27

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 1126 | 18 | GE | CJ | | 10-0 | 78-34-51 | D41462J | 7 | 18 | | TB0161C | C029 | 2 | | 001-099 |
| 1126 | 18 | GE | CJ | | 9-0 | 78-34-51 | D41462J | 7 | 18 | | TB0161C | C029 | 2 | | 115-199 |
| 1126Z | | | CJ | | 0-0 | 78-34-51 | TB0161C | | | AD | D41462J | | | AG | ALL |
| 1127 | 18 | GE | CP | | 5-0 | 78-34-51 | D41462J | 8 | 18 | | GD03600 | DC.. | 2 | | 001-002 |
| 1127 | 18 | GE | CP | | 6-0 | 78-34-51 | D41462J | 8 | 18 | | GD03600 | DC.. | 2 | | 003-099, 115-199 |
| 1127Z | | | CP | | 0-0 | 78-34-51 | D41462J | | | AG | GD03600 | DC.. | 2 | | ALL |
| 1138 | 22 | GA | | | 7-0 | 34-22-18 | D41473J | 7 | | | TB0163A | C011 | 2 | | 002 |
| 2001B | 24 | GL | AA | | 6-0 | 21-31-11 | D41473J | 23 | | | D02754 | 4 | | | 001-099 |
| 2001B | 24 | GL | AA | | 7-0 | 21-31-11 | D41473J | 23 | | | D02754 | 4 | | | 115-199 |
| 2001R | 24 | GL | AA | | 0-0 | 21-31-11 | D41473J | 22 | | | D02754 | 5 | | | ALL |
| 2002B | 24 | GL | AB | | 8-0 | 21-61-51 | D00586 | 1 | | | D41544J | 34 | | | 001-099 |
| 2002B | 24 | GL | A5 | | 6-0 | 21-61-51 | D00586 | 1 | | | D41544J | 34 | | | 115-199 |
| 2002R | 24 | GL | AB | | 0-0 | 21-61-51 | D00586 | 13 | | | D41544J | 33 | | | 001-099 |
| 2002R | 24 | GL | A5 | | 0-0 | 21-61-51 | D00586 | 13 | | | D41544J | 33 | | | 115-199 |
| 2003B | 22 | GL | AC | | 4-0 | 23-31-21 | D41497J | 15 | | | D40310J | 13 | | | 001-099 |
| 2003B | 22 | GL | AC | | 3-0 | 23-31-21 | D41497J | 15 | | | D40310J | 13 | | | 115-199 |
| 2003R | 22 | GL | AC | | 0-0 | 23-31-21 | D41497J | 14 | | | D40310J | 14 | | | ALL |
| 2004B | 22 | GB | GU | | 8-0 | 31-31-51 | D41473J | 5 | | | TB0166Y | C002 | BJ | | 010-099 |
| 2004B | 24 | GL | AD | | 6-0 | 31-31-32 | D41473J | 2 | | | TB0166Y | C002 | BJ | | 115-199 |
| 2004R | 22 | GB | GU | | 0-0 | 31-31-51 | D41473J | 4 | | | TB0166Y | A002 | BJ | | 010-099 |
| 2004R | 24 | GL | AD | | 0-0 | 31-31-32 | D41473J | 1 | | | TB0166Y | A002 | BJ | | 115-199 |
| 2005B | 24 | GL | AE | | 6-0 | 31-31-32 | D41473J | 5 | | | TB0166Y | C003 | BJ | | 115-199 |
| 2005R | 24 | GL | AE | | 0-0 | 31-31-32 | D41473J | 4 | | | TB0166Y | A003 | BJ | | 115-199 |
| 2006B | 24 | GL | AF | | 3-0 | 36-21-11 | D40874J | 1 | | | SM00008 | | WI | | 001-099 |
| 2006B | 24 | GL | AF | | 4-0 | 36-21-11 | D40874J | 1 | | | D40060J | 47 | | | 115-199 |
| 2006R | 24 | GL | AF | | 0-0 | 36-21-11 | D40874J | 2 | | | SM00004 | | WI | | 001-099 |
| 2006R | 24 | GL | AF | | 0-0 | 36-21-11 | D40874J | 2 | | | D40060J | 46 | | | 115-199 |
| 2007B | 24 | GL | AG | | 7-0 | SPARE | D00584 | 1 | | | D41612J | 45 | | | 115-199 |
| 2007R | 24 | GL | AG | | 0-0 | SPARE | D00584 | 13 | | | D41612J | 27 | | | 115-199 |
| 2008B | 24 | GL | AJ | | 8-0 | 21-51-12 | D00584 | 3 | | | D40060J | 32 | | | ALL |
| 2008R | 24 | GL | AJ | | 0-0 | 21-51-12 | D00584 | 5 | | | D40060J | 33 | | | ALL |
| 2009B | 24 | GL | DY | | 4-0 | 36-21-11 | SM00008 | | WI | | D40060J | 42 | | | 001-099 |
| 2009R | 24 | GL | DY | | 0-0 | 36-21-11 | SM00004 | | WI | | D40060J | 43 | | | 001-099 |
| 2010B | 24 | GL | DZ | | 4-0 | 36-21-11 | SM00008 | | WI | | D40060J | 47 | | | 001-099 |
| 2010R | 24 | GL | DZ | | 0-0 | 36-21-11 | SM00004 | | WI | | D40060J | 46 | | | 001-099 |
| 2011B | 24 | GL | EA | | 12-0 | 21-51-12 | SM00016 | | WI | | D41544J | 11 | | | 001-099 |
| 2011R | 24 | GL | EA | | 0-0 | 21-51-12 | D04052 | 4 | | | D41544J | 21 | | | 001-099 |
| 2012B | 24 | GL | EB | | 12-0 | 21-51-12 | SM00016 | | WI | | D41544J | 10 | | | 001-099 |
| 2012R | 24 | GL | EB | | 0-0 | 21-51-12 | D04052 | 5 | | | D41544J | 9 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 28

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 2013B | 24 | GL | EC | | 12-0 | 21-51-14 | D04138 | | 8 | | D40060J | | 2 | | 001-099 |
| 2013R | 24 | GL | EC | | 0-0 | 21-51-14 | D04138 | | 4 | | D40060J | | 3 | | 001-099 |
| 2014B | 24 | GL | ED | | 12-0 | 21-51-14 | D04138 | | 5 | | D40060J | | 18 | | 001-099 |
| 2014R | 24 | GL | ED | | 0-0 | 21-51-14 | D04138 | | 1 | | D40060J | | 4 | | 001-099 |
| 2015B | 24 | GL | EE | | 12-0 | 21-51-14 | D04138 | | 2 | | D40060J | | 54 | | 001-099 |
| 2015R | 24 | GL | EE | | 0-0 | 21-51-14 | D04138 | | 6 | | D40060J | | 55 | | 001-099 |
| 2019B | 22 | GL | BK | | 8-0 | 23-31-19 | D01457 | | 2 | | D41497J | | 42 | | 001-099 |
| 2019R | 22 | GL | BK | | 0-0 | 23-31-19 | D01457 | | 4 | | D41497J | | 41 | | 001-099 |
| 2020B | 22 | GL | BL | | 8-0 | 23-31-19 | D01457 | | 1 | | D41497J | | 44 | | 001-099 |
| 2020R | 22 | GL | BL | | 0-0 | 23-31-19 | D01457 | | 5 | | D41497J | | 45 | | 001-099 |
| 2021B | 22 | GL | BM | | 8-0 | 23-31-19 | D01457 | | 13 | | D41497J | | 31 | | 001-099 |
| 2021R | 22 | GL | BM | | 0-0 | 23-31-19 | D01457 | | 3 | | D41497J | | 30 | | 001-099 |
| 2503B | 22 | X2 | CE | | 9-0 | 34-61-16 | D02275 | | 1 | | D43019J | | 4 | | 115-199 |
| 2503R | 22 | X2 | CE | | 0-0 | 34-61-16 | D02275 | | 5 | | D43019J | | 3 | | 115-199 |
| 2503Z | | | CE | | 0-0 | 34-61-16 | GD01673 | ST.. | 2 | | D43019J | | 5 | | 115-199 |
| 2504B | 22 | X2 | CF | | 4-0 | 34-61-16 | D02275 | | 6 | | TB0161Y | A017 | BJ | | 115-199 |
| 2504R | 22 | X2 | CF | | 0-0 | 34-61-16 | D02275 | | 2 | | TB0161Y | C017 | BJ | | 115-199 |
| 2504Z | | | CF | | 0-0 | 34-61-16 | GD01673 | ST.. | 2 | | TB0161G | A014 | BJ | | 115-199 |
| 2505B | 22 | X2 | CG | | 9-0 | 34-61-16 | TB0161Y | A017 | BJ | | D43019J | | 7 | | 115-199 |
| 2505R | 22 | X2 | CG | | 0-0 | 34-61-16 | TB0161Y | C017 | BJ | | D43019J | | 6 | | 115-199 |
| 2505Z | | | CG | | 0-0 | 34-61-16 | TB0161G | A014 | BJ | | D43019J | | 8 | | 115-199 |
| 2507B | 22 | X2 | CH | | 9-0 | 34-61-16 | TB0161Y | A018 | BJ | | D43019J | | 10 | | 115-199 |
| 2507R | 22 | X2 | CH | | 0-0 | 34-61-16 | TB0161Y | C018 | BJ | | D43019J | | 9 | | 115-199 |
| 2507Z | | | CH | | 0-0 | 34-61-16 | TB0161G | A012 | BJ | | D43019J | | 11 | | 115-199 |
| 2508B | 22 | X2 | CQ | | 9-0 | 34-61-16 | D02279 | | 1 | | D43019J | | 13 | | 115-199 |
| 2508R | 22 | X2 | CQ | | 0-0 | 34-61-16 | D02279 | | 5 | | D43019J | | 12 | | 115-199 |
| 2508Z | | | CQ | | 0-0 | 34-61-16 | GD01673 | ST.. | 2 | | D43019J | | 14 | | 115-199 |
| 2509B | 22 | X2 | CR | | 9-0 | 34-61-16 | D02279 | | 8 | | D43019J | | 16 | | 115-199 |
| 2509R | 22 | X2 | CR | | 0-0 | 34-61-16 | D02279 | | 4 | | D43019J | | 15 | | 115-199 |
| 2509Z | | | CR | | 0-0 | 34-61-16 | GD01673 | ST.. | 2 | | D43019J | | 17 | | 115-199 |
| 2510B | 22 | X2 | CS | | 9-0 | 34-61-16 | D02279 | | 6 | | D43019J | | 21 | | 115-199 |
| 2510R | 22 | X2 | CS | | 0-0 | 34-61-16 | D02279 | | 2 | | D43019J | | 20 | | 115-199 |
| 2510Z | | | CS | | 0-0 | 34-61-16 | GD01673 | ST.. | 2 | | D43019J | | 22 | | 115-199 |
| 2512B | 22 | X2 | CB | | 8-0 | 34-22-38 | D41493J | | 23 | | D01515 | | B2 | | 115-199 |
| 2512R | 22 | X2 | CB | | 0-0 | 34-22-38 | D41493J | | 22 | | D01515 | | A2 | | 115-199 |
| 2512Z | | | CB | | 0-0 | 34-22-38 | D41493J | | 24 | | GD02867 | ST.. | 2 | | 115-199 |
| 2513B | 22 | X2 | CA | | 9-0 | 34-22-38 | D41475J | | 50 | | D01515 | | D2 | | 115-199 |
| 2513R | 22 | X2 | CA | | 0-0 | 34-22-38 | D41475J | | 52 | | D01515 | | C2 | | 115-199 |
| 2513Z | | | CA | | 0-0 | 34-22-38 | D41475J | | 51 | | GD02867 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 29

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | | | | | |
|--------------|-----------------|---|-------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|--|--|--|--|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | | |
| W1260 | 286N1260 | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | | | | | | | |
| 2514B | 22 | X2 | CD | 10-0 | 34-22-38 | TB0161Y | A018 | BJ | D01515 | B1 | | | 115-199 | | | | | | |
| 2514R | 22 | X2 | CD | 0-0 | 34-22-38 | TB0161Y | C018 | BJ | D01515 | A1 | | | 115-199 | | | | | | |
| 2514Z | | | CD | 0-0 | 34-22-38 | TB0161G | A012 | BJ | GD02867 | ST.. | 2 | | 115-199 | | | | | | |
| 2515B | 22 | X2 | CC | 10-0 | 34-22-38 | TB0161Y | A017 | BJ | D01515 | B3 | | | 115-199 | | | | | | |
| 2515R | 22 | X2 | CC | 0-0 | 34-22-38 | TB0161Y | C017 | BJ | D01515 | A3 | | | 115-199 | | | | | | |
| 2515Z | | | CC | 0-0 | 34-22-38 | TB0161G | A014 | BJ | GD02867 | ST.. | 2 | | 115-199 | | | | | | |
| 2517B | 22 | X2 | BX | 9-0 | 34-22-38 | D41497J | 24 | | D01515 | D1 | | | 115-199 | | | | | | |
| 2517R | 22 | X2 | BX | 0-0 | 34-22-38 | D41497J | 21 | | D01515 | C1 | | | 115-199 | | | | | | |
| 2517Z | | | BX | 0-0 | 34-22-38 | D41497J | 25 | | GD02867 | ST.. | 2 | | 115-199 | | | | | | |
| 2518B | 22 | X2 | BZ | 9-0 | 34-22-38 | D43019J | 24 | | D01515 | D3 | | | 115-199 | | | | | | |
| 2518R | 22 | X2 | BZ | 0-0 | 34-22-38 | D43019J | 23 | | D01515 | C3 | | | 115-199 | | | | | | |
| 2518Z | | | BZ | 0-0 | 34-22-38 | D43019J | 25 | | GD02867 | ST.. | 2 | | 115-199 | | | | | | |
| 2539B | 22 | X2 | CI | 9-0 | 34-61-16 | D02275 | 8 | | D43019J | 45 | | | 115-199 | | | | | | |
| 2539R | 22 | X2 | CI | 0-0 | 34-61-16 | D02275 | 4 | | D43019J | 44 | | | 115-199 | | | | | | |
| 2539Z | | | CI | 0-0 | 34-61-16 | GD01673 | ST.. | 2 | D43019J | 46 | | | 115-199 | | | | | | |
| 3001B | 22 | GM | AH | 2-0 | 21-31-31 | D40206J | 7 | | D40874J | 4 | | | 001-099 | | | | | | |
| 3001B | 22 | GM | AH | 7-0 | 21-31-31 | D40206J | 7 | | D40874J | 4 | | | 115-199 | | | | | | |
| 3001R | 22 | GM | AH | 0-0 | 21-31-31 | D40206J | 5 | | D40874J | 5 | | | ALL | | | | | | |
| 3001Y | 22 | GM | AH | 0-0 | 21-31-31 | D40206J | 6 | | D40874J | 3 | | | ALL | | | | | | |
| 3003B | 24 | GM | BY | 7-0 | 28-41-14 | D06914 | 13 | | D40608J | 20 | | | 001-099 | | | | | | |
| 3003B | 24 | GM | BY | 10-0 | 28-41-14 | D06914 | 13 | | D40608J | 20 | | | 115-199 | | | | | | |
| 3003R | 24 | GM | BY | 0-0 | 28-41-14 | D06914 | 1 | | D40608J | 26 | | | ALL | | | | | | |
| 3003Y | 24 | GM | BY | 0-0 | 28-41-14 | D06914 | 2 | | D40608J | 22 | | | ALL | | | | | | |
| 5004B | 22 | G2 | AN | 8-0 | 32-42-11 | D04342 | 1 | | D40608J | 8 | | | ALL | | | | | | |
| 5004R | 22 | G2 | AN | 0-0 | 32-42-11 | D04342 | 5 | | D40608J | 9 | | | ALL | | | | | | |
| 5004Z | | | AN | 0-0 | 32-42-11 | GD01674 | ST.. | 2 | D40608J | 10 | | | ALL | | | | | | |
| 5005B | 22 | G2 | AP | 7-0 | 32-42-11 | D04342 | 8 | | D41473J | 43 | | | ALL | | | | | | |
| 5005R | 22 | G2 | AP | 0-0 | 32-42-11 | D04342 | 4 | | D41473J | 44 | | | ALL | | | | | | |
| 5005Z | | | AP | 0-0 | 32-42-11 | GD01674 | ST.. | 2 | D41473J | 45 | | | ALL | | | | | | |
| 5006B | 22 | G2 | AQ | 8-0 | 32-42-11 | D04342 | 6 | | D41544J | 36 | | | 001-099 | | | | | | |
| 5006B | 22 | G2 | AQ | 7-0 | 32-42-11 | D04342 | 6 | | SM00018 | | WI | | 115-199 | | | | | | |
| 5006R | 22 | G2 | AQ | 0-0 | 32-42-11 | D04342 | 2 | | D41544J | 35 | | | 001-099 | | | | | | |
| 5006R | 22 | G2 | AQ | 0-0 | 32-42-11 | D04342 | 2 | | SM00019 | | WI | | 115-199 | | | | | | |
| 5006Z | | | AQ | 0-0 | 32-42-11 | GD01674 | ST.. | 2 | D41544J | 37 | | | 001-099 | | | | | | |
| 5006Z | | | AQ | 0-0 | 32-42-11 | GD01674 | ST.. | 2 | SM00020 | | WI | | 115-199 | | | | | | |
| 5007B | 24 | G2 | AO | 7-0 | 34-61-15 | D02524 | B2 | | D41475J | 26 | | | ALL | | | | | | |
| 5007R | 24 | G2 | AO | 0-0 | 34-61-15 | D02524 | A2 | | D41475J | 27 | | | ALL | | | | | | |
| 5007Z | | | AO | 0-0 | 34-61-15 | GD01693 | ST.. | 2 | D41475J | 28 | | | ALL | | | | | | |
| 5008B | 24 | G2 | BA | 7-0 | 34-61-15 | D02524 | B1 | | D41475J | 30 | | | ALL | | | | | | |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 30

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5008R | 24 | G2 | BA | | 0-0 | 34-61-15 | D02524 | A1 | | | D41475J | 29 | | | ALL |
| 5008Z | | | BA | | 0-0 | 34-61-15 | GD01693 | ST.. | 2 | | D41475J | 31 | | | ALL |
| 5009B | 24 | G2 | AI | | 7-0 | 34-61-15 | D02524 | B3 | | | D41475J | 24 | | | ALL |
| 5009R | 24 | G2 | AI | | 0-0 | 34-61-15 | D02524 | A3 | | | D41475J | 23 | | | ALL |
| 5009Z | | | AI | | 0-0 | 34-61-15 | GD01693 | ST.. | 2 | | D41475J | 25 | | | ALL |
| 5011B | 22 | G2 | BN | | 4-0 | 32-42-11 | D41544J | 36 | | | SM00018 | | WI | | 115-199 |
| 5011R | 22 | G2 | BN | | 0-0 | 32-42-11 | D41544J | 35 | | | SM00019 | | WI | | 115-199 |
| 5011Z | | | BN | | 0-0 | 32-42-11 | D41544J | 37 | | | SM00020 | | WI | | 115-199 |
| 5012B | 24 | G2 | BO | | 4-0 | 27-32-11 | D41475J | 54 | | | SM00018 | | WI | | 115-199 |
| 5012R | 24 | G2 | BO | | 0-0 | 27-32-11 | D41475J | 53 | | | SM00019 | | WI | | 115-199 |
| 5012Z | | | BO | | 0-0 | 27-32-11 | D41475J | 55 | | | SM00020 | | WI | | 115-199 |
| 5017B | 24 | G2 | BU | | 2-0 | 34-45-02 | SM00018 | | WI | | D41473J | 49 | | | 115-199 |
| 5017R | 24 | G2 | BU | | 0-0 | 34-45-02 | SM00019 | | WI | | D41473J | 48 | | | 115-199 |
| 5017Z | | | BU | | 0-0 | 34-45-02 | D41473J | 50 | | | SM00020 | | WI | | 115-199 |
| 5500 | 24 | GK | | | 3-0 | 21-25-11 | D00582 | 13 | | | TB0160Y | A027 | BJ | | ALL |
| 5502 | 20 | GK | | | 6-0 | 21-45-11 | D00594 | D2 | | | D40582J | 2 | | | 001-099 |
| 5502 | 20 | GK | | | 9-0 | 21-45-11 | D00594 | D2 | | | D40582J | 2 | | | 115-199 |
| 5503 | 20 | GK | | | 6-0 | 21-45-11 | D00594 | D1 | | * | D40582J | 3 | | | 001-099 |
| 5503 | 20 | GK | | | 4-0 | 21-45-11 | D00594 | D1 | | | TB0160Y | A001 | BJ | | 115-199 |
| 5504 | 20 | GK | | | 6-0 | 21-45-11 | D40696J | 5 | | | D00594 | D1 | | * | 001-099 |
| 5504 | 20 | GK | | | 7-0 | 21-45-11 | D40696J | 5 | | | TB0160Y | A001 | BJ | | 115-199 |
| 5505 | 20 | GK | | | 7-0 | 21-45-11 | D40582J | 3 | | | TB0160Y | A001 | BJ | | 115-199 |
| 5506 | 24 | GK | | | 8-0 | 28-25-11 | D41958J | 35 | | | D00602 | 1 | | | 001-099 |
| 5506 | 22 | GK | | | 9-0 | 28-25-11 | D41958J | 35 | | | D00602 | 1 | | | 115-199 |
| 5507 | 24 | GK | | | 2-0 | 28-25-11 | D00602 | 2 | | | GD01670 | DC.. | 2 | | 001-099 |
| 5507 | 22 | GK | | | 3-0 | 28-25-11 | D00602 | 2 | | | GD01670 | DC.. | 2 | | 115-199 |
| 5512 | 20 | GK | | | 8-0 | 21-58-11 | D01570 | 5 | | | SM00010 | | WI | | 001-099 |
| 5512 | 20 | GK | | | 7-0 | 21-58-11 | D01570 | 5 | | | SM00010 | | WI | | 115-199 |
| 5513 | 20 | GK | | | 8-0 | 21-58-11 | D01570 | 7 | | | SM00010 | | WI | | 001-099 |
| 5513 | 20 | GK | | | 7-0 | 21-58-11 | D01570 | 7 | | | SM00010 | | WI | | 115-199 |
| 5514 | 20 | GK | | | 8-0 | 21-58-11 | D41060J | 3 | | | D01572 | 6 | | | 001-099 |
| 5514 | 20 | GK | | | 7-0 | 21-58-11 | D01572 | 6 | | | D41060J | 3 | | | 115-199 |
| 5516 | 24 | GK | | | 2-0 | 21-58-11 | TB0161A | A007 | 2 | | TB0161A | A010 | 2 | | 115-199 |
| 5518 | 24 | GK | | | 7-0 | 21-58-11 | D41060J | 5 | | | TB0161A | C011 | 2 | | ALL |
| 5529 | 20 | GK | | | 2-0 | 21-58-11 | D01572 | 1 | | | TB0161Y | A015 | BJ | | 001-099 |
| 5529 | 20 | GK | | | 3-0 | 21-58-11 | D01572 | 1 | | | TB0161Y | A015 | BJ | | 115-199 |
| 5530 | 20 | GK | | | 3-0 | 21-58-11 | D01572 | 7 | | | TB0161Y | A015 | BJ | | ALL |
| 5531 | 20 | GK | | | 2-0 | 21-58-11 | D00582 | 14 | | | TB0161Y | A015 | BJ | | 001-099 |
| 5531 | 20 | GK | | | 4-0 | 21-58-11 | D00582 | 14 | | | TB0161Y | A015 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 31

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | | |
| 5532 | 20 | | GK | | 2-0 | 21-58-11 | D00582 | 7 | | | | D01570 | 2 | | | 001-099 | |
| 5532 | 20 | | GK | | 4-0 | 21-58-11 | D01570 | 2 | | | | D00582 | 7 | | | 115-199 | |
| 5533 | 24 | | GK | | 2-0 | 21-58-11 | TB0161A | A010 | 2 | | | D01570 | 1 | | | 001-099 | |
| 5533 | 24 | | GK | | 3-0 | 21-58-11 | D01570 | 1 | | | | TB0161A | A007 | 2 | | 115-199 | |
| 5534 | 20 | | GK | | 3-0 | 21-58-11 | D01570 | 3 | | | | TB0161A | A003 | 2 | | ALL | |
| 5535 | 20 | | GK | | 7-0 | 21-58-11 | D40914J | 15 | | | | D01570 | 4 | | | ALL | |
| 5536 | 24 | | GK | | 7-0 | 21-58-11 | D41060J | 2 | | | | D01570 | 8 | | | 001-099 | |
| 5536 | 24 | | GK | | 7-0 | 21-58-11 | D01570 | 8 | | | | D41060J | 2 | | | 115-199 | |
| 5540 | 24 | | GK | | 9-0 | 21-58-11 | D40874J | 10 | | | | TB0161A | A001 | 2 | | 001-099 | |
| 5540 | 24 | | GK | | 7-0 | 21-58-11 | TB0161A | C007 | 2 | | | D40874J | 10 | | | 115-199 | |
| 5544 | 24 | | GK | | 3-0 | 30-31-11 | D04184 | A3 | | | | GD01671 | AC.. | 2 | | 001-099 | |
| 5544 | 24 | | GK | | 4-0 | 30-31-11 | D04184 | A3 | | | | GD01671 | AC.. | 2 | | 115-199 | |
| 5545 | 24 | | GK | | 8-0 | 21-58-11 | D41544J | 19 | | | | TB0161A | C007 | 2 | | 115-199 | |
| 5547 | 20 | | GK | | 4-0 | 21-58-11 | D41544J | 46 | | | | SM00010 | | WI | | 115-199 | |
| 5554 | 24 | | GK | | 10-0 | 21-25-11 | D00572 | B2 | | | | D05622 | 2 | | | 001-099 | |
| 5554 | 24 | | GK | | 9-0 | 21-25-11 | D00572 | B2 | | | | D05622 | 2 | | | 115-199 | |
| 5555 | 24 | | GK | | 7-0 | 21-25-11 | D00572 | A2 | | | | D41020J | 9 | | | 001-099 | |
| 5555 | 24 | | GK | | 8-0 | 21-25-11 | D00572 | A2 | | | | D41020J | 9 | | | 115-199 | |
| 5557 | 24 | | GK | | 4-0 | 21-58-12 | D00572 | X2 | | | | TB0160A | A004 | 2 | | 001-099 | |
| 5557 | 24 | | GK | | 2-0 | 21-58-12 | D00572 | X2 | | | | TB0160A | A004 | 2 | | 115-199 | |
| 5561 | 24 | | GK | | 8-0 | 21-58-12 | D41850J | 9 | | | | TB0166A | C029 | 2 | | ALL | |
| 5568 | 16 | | GK | | 6-0 | 21-58-13 | D40918J | 6 | | | | K00343 | A1 | E | | 001-099 | |
| 5568 | 16 | | GK | | 5-0 | 21-58-13 | D40918J | 6 | | | | K00343 | A1 | E | | 115-199 | |
| 5569 | 16 | | GK | | 6-0 | 21-58-13 | D40918J | 7 | | | | K00343 | B1 | E | | 001-099 | |
| 5569 | 16 | | GK | | 5-0 | 21-58-13 | D40918J | 7 | | | | K00343 | B1 | E | | 115-199 | |
| 5570 | 16 | | GK | | 6-0 | 21-58-13 | D40918J | 8 | | | | K00343 | C1 | E | | 001-099 | |
| 5570 | 16 | | GK | | 5-0 | 21-58-13 | D40918J | 8 | | | | K00343 | C1 | E | | 115-199 | |
| 5571 | 16 | | GK | | 6-0 | 21-58-13 | D40056J | 8 | | | | K00343 | A2 | E | | 001-099 | |
| 5571 | 16 | | GK | | 5-0 | 21-58-13 | D40056J | 8 | | | | K00343 | A2 | E | | 115-199 | |
| 5572 | 16 | | GK | | 6-0 | 21-58-13 | D40056J | 6 | | | | K00343 | B2 | E | | 001-099 | |
| 5572 | 16 | | GK | | 5-0 | 21-58-13 | D40056J | 6 | | | | K00343 | B2 | E | | 115-199 | |
| 5573 | 16 | | GK | | 6-0 | 21-58-13 | K00343 | C2 | E | | | D40056J | 10 | | | 001-099 | |
| 5573 | 16 | | GK | | 8-0 | 21-58-13 | K00343 | C2 | E | | | D40056J | 10 | | | 115-199 | |
| 5574 | 16 | | GK | | 5-0 | 21-58-13 | D40056J | 1 | | | | D04266 | C3 | | | 001-099 | |
| 5574 | 16 | | GK | | 8-0 | 21-58-13 | D40056J | 1 | | | | D04266 | C3 | | | 115-199 | |
| 5578 | 16 | | GK | | 6-0 | 21-58-13 | D40056J | 2 | | | | K00343 | X2 | C | | ALL | |
| 5585 | 24 | | GK | | 6-0 | 21-58-13 | D40874J | 6 | | | | TB0163A | C004 | 2 | | 001-099 | |
| 5585 | 24 | | GK | | 7-0 | 21-58-13 | D40874J | 6 | | | | TB0163A | C004 | 2 | | 115-199 | |
| 5588 | 18 | | GK | | 7-0 | 21-58-21 | D04234 | A1 | | | | D40696J | 3 | 18 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 32

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5588 | 18 | | GK | | 6-2 | 21-58-21 | | D04234 | | A1 | | D40696J | 3 | 18 | | 115-199 |
| 5589 | 18 | | GK | | 7-0 | 21-58-21 | | D04234 | | B1 | | D40696J | 22 | 18 | | 001-099 |
| 5589 | 18 | | GK | | 6-2 | 21-58-21 | | D04234 | | B1 | | D40696J | 22 | 18 | | 115-199 |
| 5590 | 18 | | GK | | 7-0 | 21-58-21 | | D04234 | | C1 | * | D40696J | 11 | 18 | | 001-099 |
| 5590 | 18 | | GK | | 6-2 | 21-58-21 | | D04234 | | C1 | * | D40696J | 11 | 18 | | 115-199 |
| 5591 | 18 | | GK | | 9-0 | 21-58-21 | | D04234 | | A2 | | D40206J | 18 | | | 001-099 |
| 5591 | 18 | | GK | | 8-0 | 21-58-21 | | D04234 | | A2 | | D40206J | 18 | | | 115-199 |
| 5592 | 18 | | GK | | 7-0 | 21-58-21 | | D04234 | | B2 | | D40206J | 16 | | | 001-099 |
| 5592 | 18 | | GK | | 8-0 | 21-58-21 | | D04234 | | B2 | | D40206J | 16 | | | 115-199 |
| 5593 | 18 | | GK | | 7-0 | 21-58-21 | | D04234 | | C2 | | D40206J | 14 | | | 001-099 |
| 5593 | 18 | | GK | | 8-0 | 21-58-21 | | D04234 | | C2 | | D40206J | 14 | | | 115-199 |
| 5594 | 20 | | GK | | 3-0 | 21-58-21 | | D41020J | | 52 | | D40206J | 2 | | | ALL |
| 5602 | 16 | | GK | | 9-0 | 21-25-11 | | D02596 | | X2 | | D00572 | C3 | | | 001-099 |
| 5602 | 16 | | GK | | 10-0 | 21-25-11 | | D02596 | | X2 | | D00572 | C3 | | | 115-199 |
| 5608 | 16 | | GK | | 10-0 | 21-25-11 | | D02596 | | X1 | | D40910J | 4 | | | 001-099 |
| 5608 | 16 | | GK | | 8-0 | 21-25-11 | | D02596 | | X1 | | D40910J | 4 | | | 115-199 |
| 5612 | 22 | | GK | | 8-0 | 21-58-24 | | D05616 | | A1 | | D41544J | 31 | | | 115-199 |
| 5618 | 22 | | GK | | 6-0 | 21-58-24 | | D40696J | | 19 | | D04210 | C1 | | * | 115-199 |
| 5619 | 22 | | GK | | 6-0 | 21-58-24 | | D40696J | | 15 | | D04210 | B1 | | | 115-199 |
| 5620 | 22 | | GK | | 6-0 | 21-58-24 | | D40696J | | 14 | | D04210 | A1 | | | 115-199 |
| 5621 | 22 | | GK | | 8-0 | 21-58-24 | | D04210 | | C2 | | D41544J | 29 | | | 115-199 |
| 5622 | 22 | | GK | | 8-0 | 21-58-24 | | D04210 | | B2 | | D41544J | 28 | | | 115-199 |
| 5623 | 22 | | GK | | 8-0 | 21-58-24 | | D04210 | | A2 | | D41544J | 27 | | | 115-199 |
| 5624 | 22 | | GK | | 2-0 | 21-58-24 | | D04210 | | X1 | | D04210 | C1 | | * | 115-199 |
| 5625 | 24 | | GK | | 5-0 | 21-58-24 | | D40582J | | 6 | | TB0163A | C003 | 2 | | 115-199 |
| 5626 | 22 | | GK | | 8-0 | 21-58-24 | | D41544J | | 30 | | D04210 | X2 | | | 115-199 |
| 5628 | 22 | | GK | | 2-0 | 22-14-31 | | D00588 | | 7 | | TB0160Y | C002 | BJ | | 001-099 |
| 5628 | 22 | | GK | | 3-0 | 22-14-31 | | D00588 | | 7 | | TB0160Y | C002 | BJ | | 115-199 |
| 5629 | 22 | | GK | | 2-0 | 22-14-31 | | D00588 | | 11 | | TB0160Y | C002 | BJ | | 001-099 |
| 5629 | 22 | | GK | | 3-0 | 22-14-31 | | D00588 | | 11 | | TB0160Y | C002 | BJ | | 115-199 |
| 5630 | 22 | | GK | | 7-0 | 22-14-31 | | D41473J | | 9 | | TB0160Y | C002 | BJ | | 001-099 |
| 5630 | 22 | | GK | | 6-0 | 22-14-31 | | D41473J | | 9 | | TB0160Y | C002 | BJ | | 115-199 |
| 5631 | 22 | | GK | | 2-0 | 22-14-31 | | D00588 | | 1 | | TB0160Y | A005 | BJ | | 001-099 |
| 5631 | 22 | | GK | | 3-0 | 22-14-31 | | D00588 | | 1 | | TB0160Y | A005 | BJ | | 115-199 |
| 5632 | 22 | | GK | | 2-0 | 22-14-31 | | D00588 | | 5 | | TB0160Y | A005 | BJ | | 001-099 |
| 5632 | 22 | | GK | | 3-0 | 22-14-31 | | D00588 | | 5 | | TB0160Y | A005 | BJ | | 115-199 |
| 5633 | 22 | | GK | | 8-0 | 22-14-31 | | D41475J | | 45 | | TB0160Y | A005 | BJ | | ALL |
| 5634 | 22 | | GK | | 2-0 | 22-14-31 | | D00588 | | 8 | | GD01674 | DC.. | 2 | | 001-099 |
| 5634 | 22 | | GK | | 3-0 | 22-14-31 | | D00588 | | 8 | | GD01674 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 33

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 5635 | 22 | GK | | | 2-0 | 22-14-31 | D00588 | | 10 | | GD01674 | DC.. | 2 | | 001-099 |
| 5635 | 22 | GK | | | 3-0 | 22-14-31 | D00588 | | 10 | | GD01674 | DC.. | 2 | | 115-199 |
| 5636 | 22 | GK | | | 2-0 | 22-14-31 | D00588 | | 2 | | GD01674 | DC.. | 2 | | 001-099 |
| 5636 | 22 | GK | | | 3-0 | 22-14-31 | D00588 | | 2 | | GD01674 | DC.. | 2 | | 115-199 |
| 5637 | 22 | GK | | | 2-0 | 22-14-31 | D00588 | | 4 | | GD01674 | DC.. | 2 | | 001-099 |
| 5637 | 22 | GK | | | 3-0 | 22-14-31 | D00588 | | 4 | | GD01674 | DC.. | 2 | | 115-199 |
| 5642 | 24 | GK | | | 9-0 | 22-32-15 | D00590 | | 2 | | D41473J | | 11 | | 001-099 |
| 5642 | 24 | GK | | | 7-0 | 22-32-15 | D00590 | | 2 | | D41473J | | 11 | | 115-199 |
| 5643 | 24 | GK | | | 9-0 | 22-32-15 | D00590 | | 1 | | D41473J | | 12 | | 001-099 |
| 5643 | 24 | GK | | | 7-0 | 22-32-15 | D00590 | | 1 | | D41473J | | 12 | | 115-199 |
| 5644 | 24 | GK | | | 7-0 | SPARE | D00582 | | 3 | | D41497J | | 3 | | 115-199 |
| 5645 | 24 | GK | | | 3-0 | SPARE | D00582 | | 5 | | GD01674 | DC.. | 2 | | 115-199 |
| 5646 | 24 | GK | | | 7-0 | SPARE | D02768 | | 1 | | D41497J | | 4 | | 115-199 |
| 5647 | 24 | GK | | | 4-0 | SPARE | D02768 | | 2 | | GD01674 | DC.. | 2 | | 115-199 |
| 5648 | 24 | GK | | | 8-0 | 23-31-13 | D02708 | | B3 | | D41020J | | 11 | | 001-099 |
| 5648 | 24 | GK | | | 9-0 | 23-31-13 | D02708 | | B3 | | D41020J | | 11 | | 115-199 |
| 5649 | 24 | GK | | | 8-0 | 23-31-13 | D02708 | | B2 | | D41497J | | 5 | | 001-099 |
| 5649 | 24 | GK | | | 9-0 | 23-31-13 | D02708 | | B2 | | D41497J | | 5 | | 115-199 |
| 5650 | 22 | GK | | | 6-0 | 23-71-11 | D01780 | | 5 | | D41473J | | 24 | | ALL |
| 5651 | 22 | GK | | | 2-0 | 23-71-11 | D01780 | | 4 | | D02768 | | 8 | | 001-099 |
| 5651 | 22 | GK | | | 3-0 | 23-71-11 | D01780 | | 4 | | D02768 | | 8 | | 115-199 |
| 5652 | 22 | GK | | | 7-0 | 23-71-11 | D02768 | | 7 | | D41473J | | 25 | | ALL |
| 5655 | 24 | GK | | | 6-0 | 24-22-22 | D01784 | | 11 | | D40542J | | 10 | | 001-099 |
| 5655 | 24 | GK | | | 8-0 | 24-22-22 | D01784 | | 11 | | D40542J | | 10 | | 115-199 |
| 5656 | 24 | GK | | | 3-0 | 24-22-22 | D01784 | | 9 | | TB0160Y | A002 | BJ | | 001-099 |
| 5656 | 24 | GK | | | 7-0 | 24-22-22 | D01784 | | 9 | | TB0168Y | C012 | BJ | | 115-199 |
| 5657 | 24 | GK | | | 7-0 | 30-31-11 | TB0160A | A015 | 2 | | D41020J | | 3 | | 001-099 |
| 5657 | 24 | GK | | | 7-0 | 30-31-11 | TB0160C | A024 | 2 | | D41020J | | 3 | | 115-199 |
| 5658 | 24 | GK | | | 3-0 | 30-31-11 | D04184 | | B1 | | TB0160A | A016 | 2 | | 001-099 |
| 5658 | 24 | GK | | | 4-0 | 30-31-11 | D04184 | | B1 | | TB0160C | A025 | 2 | | 115-199 |
| 5661 | 22 | GK | | | 8-0 | 27-23-11 | D00598 | | D2 | | D40582J | | 33 | | 001-099 |
| 5661 | 22 | GK | | | 6-0 | 27-23-11 | D00598 | | D2 | | D40582J | | 33 | | 115-199 |
| 5662 | 22 | GK | | | 8-0 | 27-23-11 | D00598 | | D3 | * | D40574J | | 6 | | 001-099 |
| 5662 | 22 | GK | | | 6-0 | 27-23-11 | D00598 | | D3 | | TB0168Y | C022 | BJ | | 115-199 |
| 5663 | 22 | GK | | | 8-0 | 27-23-11 | D00598 | | D1 | | D40574J | | 5 | | 001-099 |
| 5663 | 22 | GK | | | 7-0 | 27-23-11 | D00598 | | D1 | | D41475J | | 40 | | 115-199 |
| 5664 | 22 | GK | | | 9-0 | 27-23-11 | D41612J | | 22 | | D00596 | | D3 | * | 001-099 |
| 5664 | 22 | GK | | | 7-0 | 27-23-11 | D41612J | | 22 | | TB0160Y | C005 | BJ | | 115-199 |
| 5665 | 22 | GK | | | 7-0 | 27-23-11 | D40874J | | 13 | | TB0160Y | C005 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 34

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5666 | 22 | | GK | | 9-0 | 27-23-11 | D00596 | | D3 | * | D40874J | 13 | | | 001-099 |
| 5666 | 22 | | GK | | 4-0 | 27-23-11 | D00596 | | D3 | | TB0160Y | C005 | BJ | | 115-199 |
| 5667 | 22 | | GK | | 9-0 | 27-23-11 | D00596 | | D1 | | D41612J | 21 | | | 001-099 |
| 5667 | 22 | | GK | | 7-0 | 27-23-11 | D00596 | | D1 | | D41612J | 21 | | | 115-199 |
| 5668 | 22 | | GK | | 9-0 | 27-23-11 | D00596 | | D2 | | D40874J | 14 | | | 001-099 |
| 5668 | 22 | | GK | | 7-0 | 27-23-11 | D00596 | | D2 | | D40874J | 14 | | | 115-199 |
| 5669 | 24 | | GK | | 4-0 | 27-32-11 | D01780 | | 14 | | TB0160Y | C005 | BJ | | 001-099 |
| 5669 | 24 | | GK | | 4-0 | 27-32-11 | D01780 | | 14 | | TB0160Y | A026 | BJ | | 115-199 |
| 5670 | 24 | | GK | | 2-0 | 27-32-11 | D01780 | | 7 | | GD01674 | DC.. | 2 | | 001-099 |
| 5670 | 24 | | GK | | 4-0 | 27-32-11 | D01780 | | 7 | | GD01674 | DC.. | 2 | | 115-199 |
| 5673 | 20 | | GK | | 10-0 | 27-62-11 | D01782 | | 5 | | D03194 | A1 | | * | 001-099 |
| 5673 | 20 | | GK | | 6-0 | 27-62-11 | D01782 | | 5 | | TB0168Y | A004 | BJ | | 115-199 |
| 5674 | 20 | | GK | | 6-0 | 27-62-11 | D01782 | | 4 | | TB0168X | D009 | BJ | | 115-199 |
| 5679 | 22 | | GK | | 9-0 | 30-21-11 | D01506 | | X1 | | TB0168Y | C016 | BJ | | 001-099 |
| 5679 | 22 | | GK | | 7-0 | 30-21-11 | D01506 | | X1 | | TB0168Y | C016 | BJ | | 115-199 |
| 5680 | 22 | | GK | | 10-0 | 30-21-11 | D41850J | | 11 | | TB0160Y | C018 | BJ | | 001-099 |
| 5680 | 22 | | GK | | 8-0 | 30-21-11 | D41850J | | 11 | | TB0160Y | A006 | BJ | | 115-199 |
| 5681 | 22 | | GK | | 9-0 | 30-21-11 | D41958J | | 20 | | TB0160Y | C018 | BJ | | 001-099 |
| 5681 | 22 | | GK | | 8-0 | 30-21-11 | D41958J | | 20 | | TB0160Y | A006 | BJ | | 115-199 |
| 5682 | 22 | | GK | | 3-0 | 30-21-11 | D01504 | | A2 | | D06326 | 7 | | | 001-099 |
| 5682 | 22 | | GK | | 4-0 | 30-21-11 | D01504 | | A2 | | D06326 | 7 | | | 115-199 |
| 5683 | 22 | | GK | | 8-0 | 30-21-11 | D40728J | | 27 | | D01504 | X1 | | * | ALL |
| 5685 | 22 | | GK | | 3-0 | 30-21-11 | D01506 | | X2 | | GD01673 | DC.. | 2 | | ALL |
| 5686 | 22 | | GK | | 9-0 | 30-21-11 | D41850J | | 47 | | D01504 | A1 | | | 001-099 |
| 5686 | 22 | | GK | | 8-0 | 30-21-11 | D41850J | | 47 | | D01504 | A1 | | | 115-199 |
| 5687 | 22 | | GK | | 3-0 | 30-21-11 | D01504 | | A3 | | TB0161A | A004 | 2 | | 001-099 |
| 5687 | 22 | | GK | | 3-0 | 30-21-11 | TB0161A | A004 | 2 | | D01504 | A3 | | | 115-199 |
| 5688 | 24 | | GK | | 7-0 | 30-31-11 | D04184 | | B2 | | D40874J | 38 | | | ALL |
| 5689 | 22 | | GK | | 7-0 | 30-21-11 | D41850J | | 10 | | TB0168Y | C016 | BJ | | 001-099 |
| 5689 | 22 | | GK | | 6-0 | 30-21-11 | D41850J | | 10 | | TB0168Y | C016 | BJ | | 115-199 |
| 5690 | 22 | | GK | | 10-0 | 30-21-11 | D41958J | | 22 | | D01504 | X2 | | | 001-099 |
| 5690 | 22 | | GK | | 9-0 | 30-21-11 | D41958J | | 2 | | D01504 | X2 | | | 115-199 |
| 5691 | 24 | | GK | | 3-0 | 30-31-11 | D40910J | | 7 | | D40860J | 1 | | | 115-199 |
| 5692 | 24 | | GK | | 3-0 | 30-31-11 | TB0160A | C015 | 2 | | D04184 | A1 | | | 001-099 |
| 5692 | 24 | | GK | | 4-0 | 30-31-11 | TB0160C | C024 | 2 | | D04184 | A1 | | | 115-199 |
| 5693 | 24 | | GK | | 4-0 | 30-31-11 | GD01671 | AC.. | 2 | | D04184 | B3 | | | ALL |
| 5694 | 24 | | GK | | 8-0 | 30-31-11 | D41020J | | 19 | | D04184 | C3 | | | 001-099 |
| 5694 | 24 | | GK | | 7-0 | 30-31-11 | D41020J | | 19 | | D04184 | C3 | | | 115-199 |
| 5695 | 24 | | GK | | 8-0 | 30-31-11 | D41020J | | 20 | | D04184 | D3 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 35

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5695 | 24 | | GK | | 7-0 | 30-31-11 | D41020J | | 20 | | D04184 | | D3 | | 115-199 |
| 5696 | 24 | | GK | | 7-0 | 30-31-11 | D41612J | | 52 | | D04184 | | D2 | | ALL |
| 5697 | 24 | | GK | | 7-0 | 30-31-11 | D41612J | | 53 | | D04184 | | C2 | | ALL |
| 5698 | 24 | | GK | | 7-0 | 30-31-11 | D40874J | | 37 | | D04184 | | A2 | | ALL |
| 5699 | 24 | | GK | | 7-0 | 30-31-11 | TB0160A | | C016 | 2 | D41020J | | 10 | | 001-099 |
| 5699 | 24 | | GK | | 7-0 | 30-31-11 | TB0160C | | C025 | 2 | D41020J | | 10 | | 115-199 |
| 5700 | 24 | | GK | | 6-0 | 30-31-12 | D00596 | | C2 | | D41022J | | 35 | | ALL |
| 5703 | 24 | | GK | | 6-0 | 30-31-12 | D00608 | | D2 | | D41022J | | 13 | | ALL |
| 5704 | 24 | | GK | | 6-0 | 30-31-12 | D00608 | | C2 | | D41022J | | 14 | | ALL |
| 5705 | 24 | | GK | | 6-0 | 30-31-12 | D00608 | | C1 | | D41022J | | 15 | | ALL |
| 5706 | 24 | | GK | | 6-0 | 30-31-12 | D00608 | | D1 | | D41022J | | 16 | | ALL |
| 5707 | 24 | | GK | | 6-0 | 30-33-11 | D00590 | | 5 | | D41473J | | 19 | | ALL |
| 5708 | 24 | | GK | | 6-0 | 30-33-11 | D00590 | | 3 | | D41022J | | 23 | | ALL |
| 5709 | 24 | | GK | | 6-0 | 30-33-11 | D00590 | | 4 | | D41022J | | 24 | | ALL |
| 5710 | 24 | | GK | | 6-0 | 31-41-19 | D00584 | | 10 | | D41473J | | 46 | | ALL |
| 5711 | 24 | | GK | | 2-0 | 31-41-19 | D00584 | | 11 | | GD01670 | | DC.. | 2 | ALL |
| 5712 | 24 | | GK | | 3-0 | 31-51-21 | D01784 | | 1 | | GD01670 | | DC.. | 2 | ALL |
| 5713 | 24 | | GK | | 7-0 | 31-51-21 | D01784 | | 2 | | D41473J | | 8 | | ALL |
| 5714 | 24 | | GK | | 2-0 | 31-51-33 | D01784 | | 7 | | GD01670 | | DC.. | 2 | 001-099 |
| 5714 | 24 | | GK | | 3-0 | 31-51-33 | D01784 | | 7 | | GD01671 | | DC.. | 2 | 115-199 |
| 5715 | 24 | | GK | | 7-0 | 31-51-33 | D01784 | | 8 | | D41497J | | 10 | | ALL |
| 5716 | 24 | | GK | | 7-0 | 31-51-41 | D01780 | | 2 | | D41497J | | 11 | | ALL |
| 5717 | 24 | | GK | | 4-0 | 31-51-41 | D00600 | | 7 | | GD01670 | | DC.. | 2 | 001-099 |
| 5717 | 24 | | GK | | 3-0 | 31-51-41 | D00600 | | 7 | | GD01671 | | DC.. | 2 | 115-199 |
| 5718 | 22 | | GK | | 2-0 | 32-09-11 | D01784 | | 6 | | TB0160Z | | 9 | BJ | 001-099 |
| 5718 | 22 | | GK | | 3-0 | 32-09-11 | D01784 | | 6 | | TB0160Z | | 9 | BJ | 115-199 |
| 5719 | 22 | | GK | | 7-0 | 32-09-11 | D01784 | | 12 | | D41612J | | 26 | | ALL |
| 5720 | 22 | | GK | | 2-0 | 32-09-11 | D01782 | | 6 | | TB0160Z | | 23 | BJ | 001-002 |
| 5720 | 22 | | GK | | 3-0 | 32-09-11 | D01782 | | 6 | | D00598 | | X1 | | * 003-099, 115-199 |
| 5721 | 22 | | GK | | 1-0 | 32-09-11 | TB0160Z | | 10 | BJ | TB0160Z | | 9 | BJ | ALL |
| 5722 | 22 | | GK | | 2-0 | 32-09-11 | D01780 | | 6 | | TB0160Z | | 23 | BJ | 001-099 |
| 5722 | 22 | | GK | | 3-0 | 32-09-11 | D01780 | | 6 | | TB0160Z | | 23 | BJ | 115-199 |
| 5723 | 22 | | GK | | 2-0 | 32-09-11 | D02754 | | 6 | | TB0160Z | | 9 | BJ | 001-099 |
| 5723 | 22 | | GK | | 4-0 | 32-09-11 | D02754 | | 6 | | TB0160Z | | 9 | BJ | 115-199 |
| 5724 | 22 | | GK | | 1-0 | 32-09-11 | TB0160Z | | 11 | BJ | TB0160Z | | 9 | BJ | 115-199 |
| 5726 | 22 | | GK | | 2-0 | 32-09-11 | D01782 | | 12 | | TB0160Y | | C006 | BJ | 001-002 |
| 5726 | 22 | | GK | | 3-0 | 32-09-11 | D01782 | | 12 | | TB0160Y | | C006 | BJ | 003-099, 115-199 |
| 5727 | 22 | | GK | | 7-0 | 32-09-11 | D41612J | | 4 | | D04184 | | X2 | | * 001-099 |
| 5727 | 22 | | GK | | 7-0 | 32-09-11 | D41612J | | 4 | | TB0160Z | | 14 | BJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 36

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5728 | 22 | | GK | | 7-0 | 32-09-11 | D01780 | | 12 | | D41612J | 25 | | | ALL |
| 5729 | 22 | | GK | | 2-0 | 32-09-11 | D02754 | | 12 | | TB0160Y | A006 | BJ | | 001-099 |
| 5729 | 22 | | GK | | 4-0 | 32-09-11 | D02754 | | 12 | | TB0160Z | 14 | BJ | | 115-199 |
| 5730 | 22 | | GK | | 2-0 | 32-09-11 | D00602 | | 12 | | TB0160Z | 12 | BJ | | 001-099 |
| 5730 | 22 | | GK | | 3-0 | 32-09-11 | D00602 | | 12 | | TB0160Z | 12 | BJ | | 115-199 |
| 5731 | 22 | | GK | | 7-0 | 32-09-11 | D04182 | | X2 | * | TB0160A | A003 | 2 | | 001-002 |
| 5731 | 22 | | GK | | 4-0 | 32-09-11 | D04182 | | X2 | | TB0160A | A003 | 2 | | 003-099 |
| 5731 | 22 | | GK | | 4-0 | 32-09-11 | D04182 | | X2 | * | TB0160A | A003 | 2 | | 115-199 |
| 5732 | 22 | | GK | | 8-0 | 32-09-11 | D41612J | | 2 | | TB0160Z | 12 | BJ | | 001-099 |
| 5732 | 22 | | GK | | 7-0 | 32-09-11 | D41612J | | 2 | | TB0160Z | 12 | BJ | | 115-199 |
| 5733 | 22 | | GK | | 2-0 | 32-09-11 | D00588 | | 12 | | TB0160Z | 12 | BJ | | 001-099 |
| 5733 | 22 | | GK | | 3-0 | 32-09-11 | D00588 | | 12 | | TB0160Z | 12 | BJ | | 115-199 |
| 5734 | 22 | | GK | | 2-0 | 32-09-11 | D00590 | | 12 | | TB0160Z | 12 | BJ | | 001-099 |
| 5734 | 22 | | GK | | 3-0 | 32-09-11 | D00590 | | 12 | | TB0160Z | 12 | BJ | | 115-199 |
| 5735 | 22 | | GK | | 2-0 | 32-09-11 | D00600 | | 12 | | TB0160Z | 12 | BJ | | 001-099 |
| 5735 | 22 | | GK | | 4-0 | 32-09-11 | D00600 | | 12 | | TB0160Z | 12 | BJ | | 115-199 |
| 5736 | 22 | | GK | | 2-0 | 32-09-11 | D00606 | | 12 | | TB0160A | A029 | 2 | | 001-099 |
| 5736 | 22 | | GK | | 4-0 | 32-09-11 | D00606 | | 12 | | TB0160A | A029 | 2 | | 115-199 |
| 5737 | 22 | | GK | | 2-0 | 32-09-11 | D00602 | | 6 | | TB0160Z | 9 | BJ | | 001-099 |
| 5737 | 22 | | GK | | 3-0 | 32-09-11 | D00602 | | 6 | | TB0160Z | 13 | BJ | | 115-199 |
| 5738 | 22 | | GK | | 1-0 | 32-09-11 | TB0160Z | 11 | BJ | | TB0160Z | 13 | BJ | | 115-199 |
| 5739 | 22 | | GK | | 2-0 | 32-09-11 | D00606 | | 6 | | TB0160Z | 23 | BJ | | 001-099 |
| 5739 | 22 | | GK | | 4-0 | 32-09-11 | D00606 | | 6 | | TB0160Z | 23 | BJ | | 115-199 |
| 5740 | 22 | | GK | | 2-0 | 32-09-11 | D00600 | | 6 | | TB0160Z | 10 | BJ | | 001-099 |
| 5740 | 22 | | GK | | 4-0 | 32-09-11 | D00600 | | 6 | | TB0160Z | 13 | BJ | | 115-199 |
| 5741 | 22 | | GK | | 2-0 | 32-09-11 | D00590 | | 6 | | TB0160Z | 10 | BJ | | 001-099 |
| 5741 | 22 | | GK | | 3-0 | 32-09-11 | D00590 | | 6 | | TB0160Z | 13 | BJ | | 115-199 |
| 5742 | 22 | | GK | | 2-0 | 32-09-11 | D00588 | | 6 | | TB0160Z | 10 | BJ | | 001-099 |
| 5742 | 22 | | GK | | 3-0 | 32-09-11 | D00588 | | 6 | | TB0160Z | 13 | BJ | | 115-199 |
| 5743 | 22 | | GK | | 2-0 | 32-09-11 | D00582 | | 6 | | TB0160Z | 10 | BJ | | 001-099 |
| 5743 | 22 | | GK | | 3-0 | 32-09-11 | D00582 | | 6 | | TB0160Z | 11 | BJ | | 115-199 |
| 5744 | 22 | | GK | | 2-0 | 32-09-11 | D00594 | X1 | | * | TB0160Z | 10 | BJ | | 001-099 |
| 5744 | 22 | | GK | | 4-0 | 32-09-11 | D00594 | X1 | | | TB0160Z | 11 | BJ | | 115-199 |
| 5745 | 22 | | GK | | 2-0 | 32-09-11 | D00586 | | 6 | | TB0160Z | 10 | BJ | | 001-099 |
| 5745 | 22 | | GK | | 3-0 | 32-09-11 | D00586 | | 6 | | TB0160Z | 11 | BJ | | 115-199 |
| 5746 | 22 | | GK | | 2-0 | 32-09-11 | D00584 | | 6 | | TB0160Z | 10 | BJ | | 001-099 |
| 5746 | 22 | | GK | | 3-0 | 32-09-11 | D00584 | | 6 | | TB0160Z | 11 | BJ | | 115-199 |
| 5747 | 22 | | GK | | 2-0 | 32-09-11 | D00604 | | 6 | | TB0160Z | 9 | BJ | | 001-099 |
| 5747 | 22 | | GK | | 3-0 | 32-09-11 | D00604 | | 6 | | TB0160Z | 9 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 37

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5748 | 22 | | GK | | 4-0 | 32-09-11 | D00582 | | 12 | | D00594 | | X2 | * | 001-099 |
| 5748 | 22 | | GK | | 3-0 | 32-09-11 | D00582 | | 12 | | TB0160Y | | C008 | BJ | 115-199 |
| 5749 | 22 | | GK | | 3-0 | 32-09-11 | D00594 | | X2 | * | TB0160A | | A024 | 2 | 001-099 |
| 5749 | 22 | | GK | | 4-0 | 32-09-11 | D00594 | | X2 | | TB0160Y | | C008 | BJ | 115-199 |
| 5750 | 22 | | GK | | 7-0 | 32-09-11 | D41612J | | 24 | | TB0160A | | C015 | 2 | 115-199 |
| 5751 | 22 | | GK | | 7-0 | 32-09-11 | D41612J | | 3 | | TB0160Y | | A008 | BJ | 115-199 |
| 5752 | 22 | | GK | | 3-0 | 32-09-11 | D00586 | | 12 | | TB0160Y | | A020 | BJ | 001-099 |
| 5752 | 22 | | GK | | 3-0 | 32-09-11 | D00586 | | 12 | | TB0160Y | | A008 | BJ | 115-199 |
| 5753 | 22 | | GK | | 3-0 | 32-09-11 | D00584 | | 12 | | TB0160Y | | A020 | BJ | 001-099 |
| 5753 | 22 | | GK | | 2-0 | 32-09-11 | D00584 | | 12 | | TB0160Y | | A008 | BJ | 115-199 |
| 5754 | 22 | | GK | | 3-0 | 32-09-11 | D04184 | | X2 | * | TB0160Y | | A006 | BJ | 001-099 |
| 5754 | 22 | | GK | | 4-0 | 32-09-11 | D04184 | | X2 | | TB0160Z | | 14 | BJ | 115-199 |
| 5755 | 22 | | GK | | 4-0 | 32-09-11 | D04184 | | X1 | | TB0160Z | | 9 | BJ | 115-199 |
| 5756 | 22 | | GK | | 2-0 | 32-09-11 | D00604 | | 12 | | TB0160Y | | A006 | BJ | 001-099 |
| 5756 | 22 | | GK | | 3-0 | 32-09-11 | D00604 | | 12 | | TB0160Z | | 14 | BJ | 115-199 |
| 5757 | 22 | | GK | | 2-0 | 32-09-11 | D00608 | | X2 | * | D00596 | | X2 | | 001-099 |
| 5757 | 22 | | GK | | 4-0 | 32-09-11 | D00596 | | X2 | * | TB0160A | | A028 | 2 | 115-199 |
| 5758 | 22 | | GK | | 7-0 | 32-09-11 | D41612J | | 5 | | TB0160A | | C028 | 2 | 115-199 |
| 5759 | 22 | | GK | | 1-0 | 32-09-11 | D00598 | | X2 | | TB0160A | | A029 | 2 | 001-099 |
| 5759 | 22 | | GK | | 2-0 | 32-09-11 | D00598 | | X2 | | TB0160A | | A029 | 2 | 115-199 |
| 5760 | 22 | | GK | | 7-0 | 32-09-11 | TB0160A | C028 | 2 | | D41612J | | 5 | | 001-099 |
| 5760 | 22 | | GK | | 4-0 | 32-09-11 | D00608 | | X2 | | D00596 | | X2 | * | 115-199 |
| 5761 | 22 | | GK | | 2-0 | 32-09-11 | D00598 | | X1 | | TB0160Z | | 23 | BJ | 001-002 |
| 5761 | 22 | | GK | | 3-0 | 32-09-11 | D00598 | | X1 | * | TB0160Z | | 23 | BJ | 003-099 |
| 5761 | 22 | | GK | | 4-0 | 32-09-11 | D00596 | | X1 | | TB0160Z | | 10 | BJ | 115-199 |
| 5763 | 22 | | GK | | 1-0 | 32-09-11 | D00596 | | X1 | | D00608 | | X1 | * | 001-099 |
| 5763 | 22 | | GK | | 4-0 | 32-09-11 | D00598 | | X1 | * | TB0160Z | | 23 | BJ | 115-199 |
| 5764 | 22 | | GK | | 1-0 | 32-09-11 | D00608 | | X1 | * | D00594 | | X1 | * | 001-099 |
| 5764 | 22 | | GK | | 4-0 | 32-09-11 | D00608 | | X1 | | TB0160Z | | 10 | BJ | 115-199 |
| 5769 | 22 | | GK | | 8-0 | 32-44-11 | D02768 | | 12 | | D41958J | | 46 | | ALL |
| 5770 | 22 | | GK | | 2-0 | 32-44-11 | D02768 | | 6 | | GD01670 | DC.. | 2 | | 001-099 |
| 5770 | 22 | | GK | | 4-0 | 32-44-11 | D02768 | | 6 | | GD01671 | DC.. | 2 | | 115-199 |
| 5771 | 22 | | GK | | 6-0 | 32-44-11 | D02768 | | 4 | | SM00009 | | WI | | 001-099 |
| 5771 | 22 | | GK | | 4-0 | 32-44-11 | D02768 | | 4 | | TB0161Z | | 1 | BJ | 115-199 |
| 5772 | 22 | | GK | | 12-0 | 32-44-11 | D02768 | | 5 | | D41850J | | 50 | | 001-099 |
| 5772 | 22 | | GK | | 7-0 | 32-44-11 | D02768 | | 5 | | D41958J | | 50 | | 115-199 |
| 5773 | 22 | | GK | | 7-0 | 32-44-11 | D41958J | | 45 | | TB0161Z | | 1 | BJ | 115-199 |
| 5774 | 22 | | GK | | 3-0 | 32-44-11 | D41958J | | 49 | | SM00009 | | WI | | 001-099 |
| 5774 | 22 | | GK | | 7-0 | 32-44-11 | D41958J | | 49 | | TB0161Z | | 1 | BJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 38

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | | |
| 5775 | 22 | | GK | | 3-0 | 32-44-11 | D41958J | | 44 | | | SM00009 | | WI | | 001-099 |
| 5775 | 22 | | GK | | 7-0 | 32-44-11 | D41958J | | 44 | | | TB0161Z | 1 | BJ | | 115-199 |
| 5776 | 22 | | GK | | 8-0 | 32-44-11 | D02768 | | 3 | | | D41958J | 47 | | | ALL |
| 5779 | 24 | | GK | | 6-0 | 30-31-12 | D00596 | | C1 | * | | D41022J | 32 | | | 001-099 |
| 5779 | 24 | | GK | | 4-0 | 30-31-12 | D00596 | | C1 | | | TB0160Y | C007 | BJ | | 115-199 |
| 5780 | 24 | | GK | | 1-0 | 30-31-12 | D00608 | | B1 | | | D00596 | C1 | | * | 001-099 |
| 5780 | 24 | | GK | | 4-0 | 30-31-12 | D00608 | | B1 | | | TB0160Y | C007 | BJ | | 115-199 |
| 5782 | 22 | | GK | | 7-0 | 32-61-11 | D02678 | | X2 | | | D41497J | 39 | | | ALL |
| 5783 | 22 | | GK | | 3-0 | 32-61-11 | D02678 | | X1 | * | | TB0160Z | 23 | BJ | | 001-099 |
| 5783 | 22 | | GK | | 4-0 | 32-61-11 | D02678 | | X1 | | | TB0160Z | 23 | BJ | | 115-199 |
| 5785 | 24 | | GK | | 7-0 | 34-12-12 | D00600 | | 10 | | | D41473J | 32 | | | 001-099 |
| 5785 | 24 | | GK | | 6-0 | 34-12-12 | D00600 | | 10 | | | D41473J | 32 | | | 115-199 |
| 5786 | 22 | | GK | | 7-0 | 34-12-12 | D00600 | | 11 | | | D40874J | 24 | | | ALL |
| 5788 | 24 | | GK | | 2-0 | 34-12-12 | D40582J | | 9 | | | D41473J | 31 | | | 001-099 |
| 5788 | 24 | | GK | | 6-0 | 34-12-12 | D40582J | | 9 | | | D41473J | 31 | | | 115-199 |
| 5793 | 24 | | GK | | 6-0 | 34-31-31 | D00590 | | 14 | | | D41493J | 2 | | | ALL |
| 5794 | 24 | | GK | | 3-0 | 34-31-31 | D00590 | | 7 | | | GD01671 | DC.. | 2 | | 001-099 |
| 5794 | 24 | | GK | | 3-0 | 34-31-31 | D00590 | | 7 | | | GD01670 | DC.. | 2 | | 115-199 |
| 5795 | 24 | | GK | | 7-0 | 34-46-12 | D02678 | | B1 | | | D41497J | 2 | | | ALL |
| 5796 | 24 | | GK | | 3-0 | 34-46-12 | D02678 | | B2 | | | GD01671 | DC.. | 2 | | 001-099 |
| 5796 | 24 | | GK | | 4-0 | 34-46-12 | D02678 | | B2 | | | GD01670 | DC.. | 2 | | 115-199 |
| 5797 | 24 | | GK | | 7-0 | 34-53-11 | D00590 | | 11 | | | D41497J | 8 | | | ALL |
| 5798 | 24 | | GK | | 2-0 | 34-53-11 | D00590 | | 10 | | | GD01670 | DC.. | 2 | | 001-099 |
| 5798 | 24 | | GK | | 3-0 | 34-53-11 | D00590 | | 10 | | | GD01670 | DC.. | 2 | | 115-199 |
| 5799 | 24 | | GK | | 2-0 | 34-55-11 | D01782 | | 14 | | | GD01670 | DC.. | 2 | | 001-099 |
| 5799 | 24 | | GK | | 3-0 | 34-55-11 | D01782 | | 14 | | | GD01670 | DC.. | 2 | | 115-199 |
| 5800 | 24 | | GK | | 7-0 | 34-55-11 | D01782 | | 7 | | | D41473J | 29 | | | ALL |
| 5801 | 24 | | GK | | 7-0 | 34-61-14 | D02754 | | 7 | | | D41473J | 16 | | | ALL |
| 5802 | 24 | | GK | | 3-0 | 34-61-14 | D02754 | | 8 | | | GD01674 | DC.. | 2 | | 001-099 |
| 5802 | 24 | | GK | | 4-0 | 34-61-14 | D02754 | | 8 | | | GD01674 | DC.. | 2 | | 115-199 |
| 5803 | 20 | | GK | | 6-0 | 76-11-21 | D00598 | | B1 | | | TB0168X | D018 | BJ | | 001-099 |
| 5803 | 20 | | GK | | 5-0 | 76-11-21 | D00598 | | B1 | | | TB0168X | D018 | BJ | | 115-199 |
| 5804 | 20 | | GK | | 6-0 | 76-11-21 | D00598 | | B2 | | | TB0168Z | 6 | BJ | | 001-099 |
| 5804 | 20 | | GK | | 5-0 | 76-11-21 | D00598 | | B2 | | | TB0168Z | 6 | BJ | | 115-199 |
| 5805 | 22 | | GK | | 7-0 | 78-34-11 | D00598 | | A2 | * | | D41948J | 32 | | | 001-099 |
| 5805 | 22 | | GK | | 6-0 | 78-34-11 | D00598 | | A2 | | | TB0168Y | A015 | BJ | | 115-199 |
| 5806 | 22 | | GK | | 7-0 | 78-34-11 | D00598 | | A1 | | | D41462J | 31 | | | 001-099 |
| 5806 | 22 | | GK | | 6-0 | 78-34-11 | D00598 | | A1 | | | TB0168Y | C014 | BJ | | 115-199 |
| 5816 | 22 | | GK | | 7-0 | 29-11-22 | D40874J | | 26 | | | TB0168Y | A011 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 39

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 5819 | 24 | GK | | | 9-0 | 26-15-11 | D00594 | | B3 | | D41850J | | 13 | | 001-099 |
| 5819 | 24 | GK | | | 8-0 | 26-15-11 | D00594 | | B3 | | D41850J | | 13 | | 115-199 |
| 5820 | 24 | GK | | | 3-0 | 26-15-11 | D00594 | | B2 | | GD01671 | DC.. | 2 | | 001-099 |
| 5820 | 22 | GK | | | 4-0 | 26-15-11 | D00594 | | B2 | | GD01671 | DC.. | 2 | | 115-199 |
| 5821 | 22 | GK | | | 9-0 | 32-42-11 | D40608J | | 38 | | TB0161Y | C019 | BJ | | 001-099 |
| 5821 | 22 | GK | | | 9-0 | 32-42-11 | D40608J | | 37 | | TB0161Y | C019 | BJ | | 115-199 |
| 5822 | 22 | GK | | | 2-0 | 32-42-11 | D02734 | | 3 | | TB0161Y | A019 | BJ | | 001-099 |
| 5822 | 22 | GK | | | 3-0 | 32-42-11 | D02734 | | 3 | | TB0161Y | C023 | BJ | | 115-199 |
| 5823 | 22 | GK | | | 8-0 | 32-42-11 | D41544J | | 39 | | TB0161Y | A019 | BJ | | 001-099 |
| 5823 | 22 | GK | | | 8-0 | 32-42-11 | D41544J | | 39 | | TB0161Y | C023 | BJ | | 115-199 |
| 5824 | 22 | GK | | | 3-0 | 32-42-11 | D02734 | | 8 | | GD01672 | DC.. | 2 | | ALL |
| 5825 | 22 | GK | | | 8-0 | 32-42-11 | D02734 | | 7 | | D41544J | | 38 | | ALL |
| 5826 | 22 | GK | | | 4-0 | 32-42-11 | D02734 | | 2 | | TB0161Z | | 9 | BJ | 001-099 |
| 5826 | 22 | GK | | | 3-0 | 32-42-11 | D02734 | | 2 | | TB0161Z | | 22 | BJ | 115-199 |
| 5827 | 22 | GK | | | 2-0 | 32-42-11 | D02734 | | 6 | | TB0161Z | | 8 | BJ | 001-099 |
| 5827 | 22 | GK | | | 3-0 | 32-42-11 | D02734 | | 6 | | TB0161Z | | 21 | BJ | 115-199 |
| 5828 | 22 | GK | | | 4-0 | 32-42-11 | D02736 | | 2 | | TB0161Z | | 9 | BJ | 001-099 |
| 5828 | 22 | GK | | | 3-0 | 32-42-11 | D02736 | | 2 | | TB0161Z | | 22 | BJ | 115-199 |
| 5829 | 22 | GK | | | 2-0 | 32-42-11 | D02736 | | 6 | | TB0161Z | | 8 | BJ | 001-099 |
| 5829 | 22 | GK | | | 3-0 | 32-42-11 | D02736 | | 6 | | TB0161Z | | 21 | BJ | 115-199 |
| 5830 | 22 | GK | | | 11-0 | 32-42-11 | D40608J | | 7 | | TB0161Z | | 9 | BJ | 001-099 |
| 5830 | 22 | GK | | | 9-0 | 32-42-11 | D40608J | | 7 | | TB0161Z | | 22 | BJ | 115-199 |
| 5831 | 22 | GK | | | 4-0 | 32-42-11 | D02740 | | 2 | | TB0161Z | | 9 | BJ | 001-099 |
| 5831 | 22 | GK | | | 3-0 | 32-42-11 | D02740 | | 2 | | TB0161Z | | 22 | BJ | 115-199 |
| 5832 | 22 | GK | | | 2-0 | 32-42-11 | D02738 | | 6 | | TB0161Z | | 8 | BJ | 001-099 |
| 5832 | 22 | GK | | | 3-0 | 32-42-11 | D02738 | | 6 | | TB0161Z | | 21 | BJ | 115-199 |
| 5833 | 22 | GK | | | 11-0 | 32-42-11 | D41544J | | 47 | | TB0161Z | | 8 | BJ | 001-099 |
| 5833 | 22 | GK | | | 8-0 | 32-42-11 | D41544J | | 47 | | TB0161Z | | 21 | BJ | 115-199 |
| 5834 | 22 | GK | | | 2-0 | 32-42-11 | D02740 | | 6 | | TB0161Z | | 8 | BJ | 001-099 |
| 5834 | 22 | GK | | | 3-0 | 32-42-11 | D02740 | | 6 | | TB0161Z | | 21 | BJ | 115-199 |
| 5835 | 22 | GK | | | 4-0 | 32-42-11 | D02738 | | 2 | | TB0161Z | | 9 | BJ | 001-099 |
| 5835 | 22 | GK | | | 3-0 | 32-42-11 | D02738 | | 2 | | TB0161Z | | 22 | BJ | 115-199 |
| 5836 | 22 | GK | | | 4-0 | 32-42-11 | D02736 | | 3 | | TB0161Y | C019 | BJ | | 001-099 |
| 5836 | 22 | GK | | | 3-0 | 32-42-11 | D02736 | | 3 | | TB0161Y | C019 | BJ | | 115-199 |
| 5837 | 22 | GK | | | 9-0 | 32-42-11 | D40608J | | 37 | | TB0161Y | C019 | BJ | | 001-099 |
| 5837 | 22 | GK | | | 9-0 | 32-42-11 | D40608J | | 13 | | TB0161Y | C019 | BJ | | 115-199 |
| 5838 | 22 | GK | | | 8-0 | 32-42-11 | D41544J | | 41 | | TB0161Y | C019 | BJ | | ALL |
| 5839 | 22 | GK | | | 8-0 | 32-42-11 | D02736 | | 7 | | D41544J | | 40 | | ALL |
| 5840 | 22 | GK | | | 2-0 | 32-42-11 | D02736 | | 8 | | GD01672 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 40

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5840 | 22 | | GK | | 3-0 | | 32-42-11 | D02736 | | | 8 | GD01672 | DC.. | 2 | | 115-199 |
| 5841 | 22 | | GK | | 4-0 | | 32-42-11 | D02736 | | | 4 | GD01672 | DC.. | 2 | | 001-099 |
| 5841 | 22 | | GK | | 3-0 | | 32-42-11 | D02736 | | | 4 | GD01672 | DC.. | 2 | | 115-199 |
| 5842 | 22 | | GK | | 11-0 | | 32-42-11 | D41544J | | | 48 | TB0161Z | 9 | BJ | | 001-099 |
| 5842 | 22 | | GK | | 8-0 | | 32-42-11 | D41544J | | | 48 | TB0161Z | 22 | BJ | | 115-199 |
| 5844 | 22 | | GK | | 4-0 | | 32-42-11 | D02734 | | | 4 | GD01672 | DC.. | 2 | | 001-099 |
| 5844 | 22 | | GK | | 3-0 | | 32-42-11 | D02734 | | | 4 | GD01672 | DC.. | 2 | | 115-199 |
| 5845 | 22 | | GK | | 2-0 | | 32-42-11 | D02738 | | | 8 | GD01672 | DC.. | 2 | | 001-099 |
| 5845 | 22 | | GK | | 3-0 | | 32-42-11 | D02738 | | | 8 | GD01672 | DC.. | 2 | | 115-199 |
| 5846 | 22 | | GK | | 12-0 | | 32-42-11 | D02738 | | | 7 | D41850J | 37 | | | 001-099 |
| 5846 | 22 | | GK | | 8-0 | | 32-42-11 | D02738 | | | 7 | D40728J | 32 | | | 115-199 |
| 5847 | 22 | | GK | | 2-0 | | 32-42-11 | D02738 | | | 3 | TB0161Y | A020 | BJ | | 001-099 |
| 5847 | 22 | | GK | | 3-0 | | 32-42-11 | D02738 | | | 3 | TB0161Y | A020 | BJ | | 115-199 |
| 5848 | 22 | | GK | | 9-0 | | 32-42-11 | D41850J | | | 23 | TB0161Y | A020 | BJ | | ALL |
| 5849 | 22 | | GK | | 12-0 | | 32-42-11 | D41850J | | | 38 | TB0161Y | A020 | BJ | | 001-099 |
| 5849 | 22 | | GK | | 8-0 | | 32-42-11 | D40728J | | | 33 | TB0161Y | A020 | BJ | | 115-199 |
| 5850 | 22 | | GK | | 2-0 | | 32-42-11 | D02740 | | | 8 | GD01673 | DC.. | 2 | | 001-099 |
| 5850 | 22 | | GK | | 3-0 | | 32-42-11 | D02740 | | | 8 | GD01673 | DC.. | 2 | | 115-199 |
| 5851 | 22 | | GK | | 2-0 | | 32-42-11 | D02740 | | | 3 | TB0161Y | C020 | BJ | | 001-099 |
| 5851 | 22 | | GK | | 3-0 | | 32-42-11 | D02740 | | | 3 | TB0161Y | C020 | BJ | | 115-199 |
| 5852 | 22 | | GK | | 9-0 | | 32-42-11 | D41850J | | | 24 | TB0161Y | C020 | BJ | | ALL |
| 5853 | 22 | | GK | | 12-0 | | 32-42-11 | D41850J | | | 40 | TB0161Y | C020 | BJ | | 001-099 |
| 5853 | 22 | | GK | | 8-0 | | 32-42-11 | D40728J | | | 35 | TB0161Y | C020 | BJ | | 115-199 |
| 5854 | 22 | | GK | | 12-0 | | 32-42-11 | D02740 | | | 7 | D41850J | 39 | | | 001-099 |
| 5854 | 22 | | GK | | 8-0 | | 32-42-11 | D02740 | | | 7 | D40728J | 34 | | | 115-199 |
| 5855 | 22 | | GK | | 4-0 | | 32-42-11 | D02740 | | | 4 | GD01673 | DC.. | 2 | | 001-099 |
| 5855 | 22 | | GK | | 3-0 | | 32-42-11 | D02740 | | | 4 | GD01673 | DC.. | 2 | | 115-199 |
| 5856 | 22 | | GK | | 4-0 | | 32-42-11 | D02738 | | | 4 | GD01672 | DC.. | 2 | | 001-099 |
| 5856 | 20 | | GK | | 3-0 | | 32-42-11 | D02738 | | | 4 | GD01672 | DC.. | 2 | | 115-199 |
| 5857 | 22 | | GK | | 2-0 | | 32-42-11 | D02742 | | | 8 | GD01673 | DC.. | 2 | | 001-099 |
| 5857 | 22 | | GK | | 4-0 | | 32-42-11 | D02742 | | | 8 | GD01673 | DC.. | 2 | | 115-199 |
| 5858 | 22 | | GK | | 2-0 | | 32-42-11 | D02742 | | | 3 | TB0161Y | C020 | BJ | | 001-099 |
| 5858 | 22 | | GK | | 3-0 | | 32-42-11 | D02742 | | | 3 | TB0161Y | C020 | BJ | | 115-199 |
| 5859 | 22 | | GK | | 12-0 | | 32-42-11 | D02742 | | | 7 | D41850J | 42 | | | 001-099 |
| 5859 | 22 | | GK | | 8-0 | | 32-42-11 | D02742 | | | 7 | D40728J | 36 | | | 115-199 |
| 5860 | 22 | | GK | | 7-0 | | 32-42-11 | D02742 | | | 4 | D41948J | 28 | | | 001-099 |
| 5860 | 22 | | GK | | 8-0 | | 32-42-11 | D02742 | | | 4 | D41948J | 28 | | | 115-199 |
| 5861 | 22 | | GK | | 11-0 | | 32-42-11 | D02742 | | | 6 | D41544J | 49 | | | 001-099 |
| 5861 | 22 | | GK | | 8-0 | | 32-42-11 | D02742 | | | 6 | D41544J | 49 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 41

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | | |
| 5862 | 22 | | GK | | 2-0 | 32-42-11 | | D02742 | | 2 | | TB0161Z | 9 | BJ | | 001-099 | |
| 5862 | 22 | | GK | | 3-0 | 32-42-11 | | D02742 | | 2 | | TB0161Z | 22 | BJ | | 115-199 | |
| 5864 | 18 | | GK | | 7-0 | 28-22-11 | | D04704 | | B3 | | D40582J | 28 | 18 | | ALL | |
| 5865 | 18 | | GK | | 7-0 | 28-22-11 | | D04704 | | B2 | | D40582J | 42 | 18 | | 001-099 | |
| 5865 | 18 | | GK | | 7-0 | 28-22-11 | | D04704 | | B2 | | D40582J | 29 | 18 | | 115-199 | |
| 5866 | 24 | | GK | | 8-0 | 21-25-11 | | D41060J | | 20 | | TB0165A | A001 | 2 | | 001-099 | |
| 5866 | 24 | | GK | | 7-0 | 21-25-11 | | D41060J | | 20 | | TB0165A | A001 | 2 | | 115-199 | |
| 5867 | 22 | | GK | | 7-0 | 27-09-12 | | D04706 | | 1 | | D41473J | 15 | | | ALL | |
| 5868 | 22 | | GK | | 2-0 | 27-09-12 | | D04706 | | 2 | | GD01670 | DC.. | 2 | | 001-099 | |
| 5868 | 22 | | GK | | 3-0 | 27-09-12 | | D04706 | | 2 | | GD01671 | DC.. | 2 | | 115-199 | |
| 5869 | 22 | | GK | | 7-0 | 27-09-12 | | D04708 | | 5 | | D41493J | 13 | | | 001-099 | |
| 5869 | 22 | | GK | | 6-0 | 27-09-12 | | D04708 | | 5 | | D41493J | 13 | | | 115-199 | |
| 5870 | 22 | | GK | | 7-0 | 27-09-12 | | D04708 | | 4 | | D41493J | 14 | | | 001-099 | |
| 5870 | 22 | | GK | | 6-0 | 27-09-12 | | D04708 | | 4 | | D41493J | 14 | | | 115-199 | |
| 5871 | 22 | | GK | | 7-0 | 27-09-12 | | D04708 | | 1 | | D41493J | 15 | | | 001-099 | |
| 5871 | 22 | | GK | | 6-0 | 27-09-12 | | D04708 | | 1 | | D41493J | 15 | | | 115-199 | |
| 5872 | 22 | | GK | | 7-0 | 27-09-12 | | D04708 | | 2 | | D41493J | 16 | | | 001-099 | |
| 5872 | 22 | | GK | | 6-0 | 27-09-12 | | D04708 | | 2 | | D41493J | 16 | | | 115-199 | |
| 5873 | 22 | | GK | | 7-0 | 27-09-12 | | D04708 | | 7 | | D41493J | 8 | | | 001-099 | |
| 5873 | 22 | | GK | | 6-0 | 27-09-12 | | D04708 | | 7 | | D41493J | 8 | | | 115-199 | |
| 5874 | 22 | | GK | | 2-0 | 27-09-12 | | D04708 | | 8 | | GD01670 | DC.. | 2 | | 001-099 | |
| 5874 | 22 | | GK | | 3-0 | 27-09-12 | | D04708 | | 8 | | GD01671 | DC.. | 2 | | 115-199 | |
| 5875 | 22 | | GK | | 3-0 | 27-09-12 | | D01780 | | 11 | | TB0160Y | A018 | BJ | | 001-099 | |
| 5875 | 22 | | GK | | 4-0 | 27-09-12 | | D01780 | | 11 | | TB0161Y | C024 | BJ | | 115-199 | |
| 5876 | 22 | | GK | | 2-0 | 27-09-12 | | D01780 | | 10 | | GD01670 | DC.. | 2 | | 001-099 | |
| 5876 | 22 | | GK | | 3-0 | 27-09-12 | | D01780 | | 10 | | GD01671 | DC.. | 2 | | 115-199 | |
| 5877 | 24 | | GK | | 2-0 | 21-51-13 | | D01782 | | 2 | | GD01670 | DC.. | 2 | | 001-099 | |
| 5877 | 24 | | GK | | 3-0 | 21-51-13 | | D01782 | | 2 | | GD01671 | DC.. | 2 | | 115-199 | |
| 5878 | 24 | | GK | | 8-0 | 21-51-13 | | D01782 | | 1 | | D41544J | 32 | | | ALL | |
| 5879 | 22 | | GK | | 4-0 | 77-12-41 | | D04704 | | X2 | | GD01671 | DC.. | 2 | | ALL | |
| 5880 | 22 | | GK | | 3-0 | 77-12-41 | | D04704 | | X1 | | TB0160Y | C020 | BJ | | 001-099 | |
| 5880 | 22 | | GK | | 4-0 | 77-12-41 | | D04704 | | X1 | * | TB0160Y | C020 | BJ | | 115-199 | |
| 5882 | 22 | | GK | | 8-0 | 32-42-11 | | D04342 | | 7 | | D41475J | 42 | | | 001-099 | |
| 5882 | 22 | | GK | | 7-0 | 32-42-11 | | D04342 | | 7 | | D41475J | 42 | | | 115-199 | |
| 5883 | 22 | | GK | | 2-0 | 32-42-11 | | D04342 | | 3 | | TB0161Y | A019 | BJ | | 001-099 | |
| 5883 | 22 | | GK | | 4-0 | 32-42-11 | | D04342 | | 3 | | TB0161Y | C023 | BJ | | 115-199 | |
| 5884 | 22 | | GK | | 7-0 | 32-42-11 | | D40696J | | 17 | | TB0161Y | A019 | BJ | | 001-099 | |
| 5884 | 22 | | GK | | 7-0 | 32-42-11 | | D40696J | | 17 | | TB0161Y | C023 | BJ | | 115-199 | |
| 5886 | 22 | | GK | | 8-0 | 32-42-12 | | D04510 | | 1 | | D41544J | 42 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 42

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5887 | 22 | | GK | | 8-0 | 32-42-12 | | D04510 | | 13 | | D41544J | 43 | | | ALL |
| 5888 | 22 | | GK | | 2-0 | 32-09-11 | | D04510 | | 6 | | TB0160Z | 9 | BJ | | 001-099 |
| 5888 | 22 | | GK | | 3-0 | 32-09-11 | | D04510 | | 6 | | TB0160Z | 10 | BJ | | 115-199 |
| 5889 | 22 | | GK | | 3-0 | 32-09-11 | | D04510 | | 12 | | TB0160A | A024 | 2 | | 001-099 |
| 5889 | 22 | | GK | | 3-0 | 32-09-11 | | D04510 | | 12 | | TB0160Y | C008 | BJ | | 115-199 |
| 5891 | 22 | | GK | | 3-0 | 32-09-11 | | D04706 | | 6 | | TB0160Z | 23 | BJ | | ALL |
| 5892 | 22 | | GK | | 3-0 | 32-09-11 | | D04708 | | 6 | | TB0160Z | 23 | BJ | | ALL |
| 5893 | 22 | | GK | | 2-0 | 32-09-11 | | D04706 | | 12 | | TB0160Y | C006 | BJ | | 001-099 |
| 5893 | 22 | | GK | | 3-0 | 32-09-11 | | D04706 | | 12 | | TB0160Y | C006 | BJ | | 115-199 |
| 5894 | 22 | | GK | | 2-0 | 32-09-11 | | D04708 | | 12 | | TB0160Y | C006 | BJ | | 001-099 |
| 5894 | 22 | | GK | | 3-0 | 32-09-11 | | D04708 | | 12 | | TB0160Y | C006 | BJ | | 115-199 |
| 5895 | 22 | | GK | | 8-0 | 32-09-11 | | D41612J | | 28 | | TB0160Y | C006 | BJ | | 001-099 |
| 5895 | 22 | | GK | | 7-0 | 32-09-11 | | D41612J | | 28 | | TB0160Y | C006 | BJ | | 115-199 |
| 5896 | 24 | | GK | | 6-0 | 24-51-71 | | D00602 | | 5 | | TB0168Y | C005 | BJ | | 001-099 |
| 5896 | 24 | | GK | | 6-0 | 24-51-71 | | D00602 | | 5 | | TB0168Y | C019 | BJ | | 115-199 |
| 5897 | 24 | | GK | | 7-0 | 24-51-71 | | D00602 | | 4 | | D40874J | 16 | | | ALL |
| 5898 | 22 | | GK | | 4-0 | 27-23-21 | | D04510 | | 5 | | GD01672 | DC.. | 2 | | ALL |
| 5899 | 22 | | GK | | 8-0 | 27-23-21 | | D04510 | | 3 | | D41475J | 3 | | | ALL |
| 5901 | 22 | | GK | | 7-0 | 32-09-11 | | D40696J | | 7 | | D00592 | X1 | | * | 001-099 |
| 5901 | 22 | | GK | | 8-0 | 32-09-11 | | D40696J | | 7 | | TB0160Z | 13 | BJ | | 115-199 |
| 5908 | 16 | | GK | | 4-0 | 29-11-31 | | D04726 | | A2 | | TB0166G | 10 | 2 | | 001-099 |
| 5908 | 16 | | GK | | 4-0 | 29-11-31 | | D04726 | | A2 | | TB0166G | 19 | 2 | | 115-199 |
| 5909 | 22 | | GK | | 4-0 | 29-11-31 | | D04726 | | X1 | | TB0166G | 10 | 2 | | 001-099 |
| 5909 | 22 | | GK | | 4-0 | 29-11-31 | | D04726 | | X1 | | TB0166G | 19 | 2 | | 115-199 |
| 5910 | 16 | | GK | | 7-0 | 29-11-31 | | D40874J | | 51 | 16 | TB0166G | 10 | 2 | | 001-099 |
| 5910 | 16 | | GK | | 8-0 | 29-11-31 | | D40874J | | 51 | 16 | TB0166G | 19 | 2 | | 115-199 |
| 5911 | 16 | | GK | | 8-0 | 29-11-31 | | D04726 | | A1 | | D40874J | 49 | 16 | | ALL |
| 5912 | 22 | | GK | | 8-0 | 29-11-31 | | D04726 | | X2 | | D40542J | 6 | | | 001-099 |
| 5912 | 22 | | GK | | 8-0 | 29-11-31 | | D04726 | | X2 | | TB0168Y | A003 | BJ | | 115-199 |
| 5913 | 20 | | GK | | 2-0 | 29-11-31 | | GD01690 | | DC.. | 2 | M10482 | B | C | | 001-099 |
| 5913 | 20 | | GK | | 8-0 | 29-11-31 | | GD01685 | | DC.. | 2 | M10482 | B | C | | 115-199 |
| 5916 | 22 | | GK | | 7-0 | 31-31-32 | | D02678 | | C2 | | D41497J | 30 | | | 115-199 |
| 5917 | 22 | | GK | | 6-0 | 31-31-32 | | D02678 | | C3 | | TB0168Z | 5 | BJ | | 115-199 |
| 5921 | 22 | | GK | | 3-0 | 29-11-31 | | TB0168X | | B009 | BJ | M10482 | A | C | | 115-199 |
| 5923 | 22 | | GK | | 8-0 | 32-44-11 | | D41948J | | 33 | | TB0161Z | 1 | BJ | | 115-199 |
| 5924 | 22 | | GK | | 2-0 | 32-09-11 | | D00592 | | X1 | | D04184 | X1 | | * | 001-099 |
| 5925 | 22 | | GK | | 8-0 | 32-09-11 | | D00592 | | X2 | | D41612J | 3 | | | 001-002 |
| 5925 | 22 | | GK | | 7-0 | 32-09-11 | | TB0360B | | C015 | 2 | D41612J | 3 | | | 003-099 |
| 5926 | 22 | | GK | | 3-0 | 30-32-11 | | D00592 | | C2 | | TB0160Z | 11 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 43

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 5929 | 22 | GK | | | 2-0 | 33-16-11 | D00586 | | 7 | | TB0160Y | C001 | BJ | | 001-099 |
| 5929 | 22 | GK | | | 3-0 | 33-16-11 | D00586 | | 7 | | TB0160Y | A007 | BJ | | 115-199 |
| 5930 | 22 | GK | | | 7-0 | 33-16-11 | D00586 | | 8 | | D40874J | 52 | | | ALL |
| 5931 | 22 | GK | | | 2-0 | 33-16-11 | D00604 | | 11 | | TB0160Y | C001 | BJ | | 001-099 |
| 5931 | 22 | GK | | | 3-0 | 33-16-11 | D00604 | | 11 | | TB0160Y | A007 | BJ | | 115-199 |
| 5932 | 22 | GK | | | 7-0 | 33-16-11 | D00604 | | 10 | | D40874J | 53 | | | ALL |
| 5933 | 22 | GK | | | 2-0 | 33-16-11 | D00606 | | 11 | | TB0160Y | C001 | BJ | | 001-099 |
| 5933 | 22 | GK | | | 3-0 | 33-16-11 | D00606 | | 11 | | TB0160Y | A007 | BJ | | 115-199 |
| 5934 | 22 | GK | | | 7-0 | 33-16-11 | D00606 | | 10 | | D40874J | 54 | | | ALL |
| 5935 | 22 | GK | | | 7-0 | 33-16-11 | TB0160Y | C001 | BJ | | D40874J | 55 | | | 001-099 |
| 5935 | 22 | GK | | | 7-0 | 33-16-11 | TB0160Y | A007 | BJ | | D40874J | 55 | | | 115-199 |
| 5936 | 22 | GK | | | 7-0 | 32-61-11 | D40728J | | 26 | | D02678 | X1 | | * | 001-099 |
| 5936 | 22 | GK | | | 8-0 | 32-61-11 | D40728J | | 26 | | TB0160Z | 23 | BJ | | 115-199 |
| 5937 | 22 | GK | | | 7-0 | 32-61-11 | D41497J | | 38 | | D02678 | X1 | | * | 001-099 |
| 5937 | 22 | GK | | | 8-0 | 32-61-11 | D41497J | | 38 | | TB0160Z | 23 | BJ | | 115-199 |
| 5967 | 22 | GK | | | 9-0 | 76-11-21 | D01726 | | A1 | | TB0168Z | 6 | BJ | | 001-099 |
| 5967 | 22 | GK | | | 7-0 | 76-11-21 | D01726 | | A1 | | TB0168Z | 6 | BJ | | 115-199 |
| 5968 | 20 | GK | | | 9-0 | 76-11-21 | D01726 | | X1 | | TB0168X | D018 | BJ | | 001-099 |
| 5968 | 20 | GK | | | 8-0 | 76-11-21 | D01726 | | X1 | | TB0168X | D018 | BJ | | 115-199 |
| 5969 | 20 | GK | | | 10-0 | 76-11-21 | D01726 | | A2 | | D41958J | 7 | | | 001-099 |
| 5969 | 20 | GK | | | 8-0 | 76-11-21 | D01726 | | A2 | | D41958J | 7 | | | 115-199 |
| 5970 | 22 | GK | | | 8-0 | 76-11-21 | D01726 | | X2 | | GD01690 | DC.. | 2 | | ALL |
| 5972 | 24 | GK | | | 6-0 | 30-31-12 | D00608 | | B2 | | D41022J | 29 | | | ALL |
| 5975 | 24 | GK | | | 6-0 | 21-58-12 | D00572 | | X1 | | SM00012 | | WI | | ALL |
| 5976 | 24 | GK | | | 10-0 | 73-21-11 | D05198 | | 13 | | D41948J | 29 | | | 001-099 |
| 5976 | 24 | GK | | | 8-0 | 73-21-11 | D05198 | | 13 | | D41948J | 29 | | | 115-199 |
| 5977 | 24 | GK | | | 10-0 | 73-21-11 | D05198 | | 1 | | D41948J | 31 | | | 001-099 |
| 5977 | 24 | GK | | | 8-0 | 73-21-11 | D05198 | | 1 | | D41948J | 31 | | | 115-199 |
| 5978 | 24 | GK | | | 10-0 | 73-21-12 | D05198 | | 9 | | D41948J | 34 | | | 001-099 |
| 5978 | 24 | GK | | | 8-0 | 73-21-12 | D05198 | | 9 | | D41948J | 34 | | | 115-199 |
| 5979 | 24 | GK | | | 10-0 | 73-21-12 | D05198 | | 11 | | D41948J | 35 | | | 001-099 |
| 5979 | 24 | GK | | | 8-0 | 73-21-12 | D05198 | | 11 | | D41948J | 35 | | | 115-199 |
| 5980 | 24 | GK | | | 10-0 | 73-21-12 | D05198 | | 14 | | D41948J | 36 | | | 001-099 |
| 5980 | 24 | GK | | | 8-0 | 73-21-12 | D05198 | | 14 | | D41948J | 36 | | | 115-199 |
| 5981 | 24 | GK | | | 10-0 | 73-21-12 | D05198 | | 7 | | D07002 | X1 | | * | 001-099 |
| 5981 | 24 | GK | | | 8-0 | 73-21-12 | D05198 | | 7 | | D07002 | X1 | | * | 115-199 |
| 5982 | 24 | GK | | | 10-0 | 73-21-12 | D05198 | | 3 | | D41948J | 44 | | | 001-099 |
| 5982 | 24 | GK | | | 8-0 | 73-21-12 | D05198 | | 3 | | D41948J | 38 | | | 115-199 |
| 5983 | 24 | GK | | | 3-0 | 73-21-12 | D05198 | | 5 | | GD01671 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 44

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 5983 | 24 | | GK | | 4-0 | 73-21-12 | | D05198 | | 5 | | GD01671 | DC.. | 2 | | 115-199 |
| 5984 | 22 | | GK | | 1-0 | 77-12-41 | | D05198 | | 12 | | GD01670 | DC.. | 2 | | 001-099 |
| 5984 | 20 | | GK | | 4-0 | 77-12-41 | | D05198 | | 12 | | GD01671 | DC.. | 2 | | 115-199 |
| 5985 | 22 | | GK | | 4-0 | 77-12-41 | | D05198 | | 6 | | TB0160Y | C020 | BJ | | ALL |
| 5986 | 22 | | GK | | 9-0 | 77-12-41 | | D41948J | | 30 | | TB0160Y | C020 | BJ | | 001-099 |
| 5986 | 22 | | GK | | 8-0 | 77-12-41 | | D41948J | | 30 | | TB0160Y | C020 | BJ | | 115-199 |
| 5998 | 24 | | GK | | 8-0 | 73-21-22 | | D04704 | | A2 | | D42096J | | 10 | | 001-099 |
| 5998 | 24 | | GK | | 9-0 | 73-21-22 | | D04704 | | A2 | | D42096J | | 10 | | 115-199 |
| 5999 | 24 | | GK | | 8-0 | 73-21-22 | | D04704 | | A1 | | D42096J | | 9 | | 001-099 |
| 5999 | 24 | | GK | | 9-0 | 73-21-22 | | D04704 | | A1 | | D42096J | | 9 | | 115-199 |
| 6002 | 22 | | GK | | 8-0 | 30-34-22 | | D00608 | | A2 | | D40608J | | 31 | | ALL |
| 6003 | 22 | | GK | | 8-0 | 30-34-22 | | D00608 | | A1 | | D40608J | | 32 | | ALL |
| 6004 | 22 | | GK | | 8-0 | 30-34-22 | | D00608 | | A3 | | D40608J | | 33 | | ALL |
| 6008 | 18 | | GK | | 3-0 | 30-34-21 | | D00596 | | A3 | | TB0160G | | 8 | 2 | 001-099 |
| 6008 | 18 | | GK | | 4-0 | 30-34-21 | | D00596 | | A3 | | TB0161G | | 5 | 2 | 115-199 |
| 6010 | 18 | | GK | | 3-0 | 30-34-21 | | D00596 | | A2 | | TB0160G | | 7 | 2 | 001-099 |
| 6010 | 18 | | GK | | 4-0 | 30-34-21 | | D00596 | | A2 | | TB0161G | | 6 | 2 | 115-199 |
| 6013 | 24 | | GK | | 4-0 | 21-25-11 | | D00572 | | B3 | | TB0160Y | C026 | BJ | | ALL |
| 6015 | 24 | | GK | | 3-0 | 21-25-11 | | D05501 | | 2 | | TB0160Y | C026 | BJ | | 001-099 |
| 6015 | 24 | | GK | | 4-0 | 21-25-11 | | D05501 | | 2 | | TB0160Y | C026 | BJ | | 115-199 |
| 6016 | 24 | | GK | | 3-0 | 21-25-11 | | D05501 | | 4 | | TB0160Y | A027 | BJ | | 001-099 |
| 6016 | 24 | | GK | | 4-0 | 21-25-11 | | D05501 | | 4 | | TB0160Y | A027 | BJ | | 115-199 |
| 6027 | 24 | | GK | | 1-0 | 21-58-12 | | D05190 | | B2 | * | D05190 | X2 | | * | ALL |
| 6035 | 24 | | GK | | 2-0 | 21-58-12 | | D05618 | | 3 | | TB0161A | A025 | 2 | | 001-099 |
| 6035 | 24 | | GK | | 3-0 | 21-58-12 | | D05618 | | 3 | | TB0161A | A025 | 2 | | 115-199 |
| 6040 | 24 | | GK | | 7-0 | 21-58-12 | | D05618 | | 7 | | M10689 | A | C | | 001-099 |
| 6040 | 24 | | GK | | 8-0 | 21-58-12 | | D05618 | | 7 | | M10689 | A | C | | 115-199 |
| 6042 | 24 | | GK | | 12-0 | 21-51-12 | | D04052 | | 1 | | D41544J | | 8 | | 001-099 |
| 6043 | 24 | | GK | | 5-0 | 21-51-12 | | D04052 | | 13 | | GD01687 | DC.. | 2 | | 001-099 |
| 6044 | 24 | | GK | | 7-0 | 21-51-13 | | D02950 | | D3 | | D40716J | | 11 | | 001-099 |
| 6045 | 22 | | GK | | 9-0 | 21-51-13 | | D02948 | | C2 | | D40060J | | 24 | | 001-099 |
| 6046 | 22 | | GK | | 9-0 | 21-51-13 | | D02950 | | A2 | | D40060J | | 26 | | 001-099 |
| 6047 | 22 | | GK | | 9-0 | 21-51-13 | | D02950 | | B2 | | D40060J | | 27 | | 001-099 |
| 6048 | 22 | | GK | | 9-0 | 21-51-13 | | D02950 | | C2 | | D40060J | | 28 | | 001-099 |
| 6049 | 24 | | GK | | 3-0 | 21-51-13 | | D02972 | | X1 | | TB0163Z | | 8 | BJ | 001-099 |
| 6050 | 22 | | GK | | 9-0 | 76-11-21 | | D01506 | | B2 | | TB0360X | D009 | BJ | | 001-099 |
| 6050 | 22 | | GK | | 10-0 | 76-11-21 | | D01506 | | B2 | | TB0360X | D009 | BJ | | 115-199 |
| 6051 | 22 | | GK | | 10-0 | 76-11-21 | | D01506 | | B3 | | D41493J | | 9 | | 001-099 |
| 6051 | 22 | | GK | | 7-0 | 76-11-21 | | D01506 | | B3 | | D41493J | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 45

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | |
| 6052 | 22 | GK | | | 9-0 | 76-11-21 | D05594 | | 6 | | TB0360X | B010 | BJ | | 001-099 |
| 6052 | 22 | GK | | | 10-0 | 76-11-21 | D05594 | | 6 | | TB0360X | B010 | BJ | | 115-199 |
| 6053 | 22 | GK | | | 3-0 | 76-11-21 | D05594 | | 8 | | D01726 | A3 | | | 001-099 |
| 6053 | 22 | GK | | | 4-0 | 76-11-21 | D05594 | | 8 | | D01726 | A3 | | | 115-199 |
| 6054 | 22 | GK | | | 9-0 | 76-11-21 | D05594 | | 7 | | TB0168Z | 6 | BJ | | 001-099 |
| 6054 | 22 | GK | | | 6-0 | 76-11-21 | D05594 | | 7 | | TB0168Z | 6 | BJ | | 115-199 |
| 6055 | 22 | GK | | | 10-0 | 76-11-21 | D05594 | | 3 | | D41473J | 26 | | | 001-099 |
| 6055 | 22 | GK | | | 6-0 | 76-11-21 | D05594 | | 3 | | D41473J | 26 | | | 115-199 |
| 6056 | 24 | GK | | | 9-0 | 21-51-13 | D02972 | | X2 | | D40060J | 16 | | | 001-099 |
| 6057 | 22 | GK | | | 3-0 | 21-51-13 | D02950 | | B3 | | D02972 | A2 | | | 001-099 |
| 6059 | 24 | GK | | | 3-0 | 21-51-13 | D02972 | | A1 | | TB0163Z | 9 | BJ | | 001-099 |
| 6060 | 24 | GK | | | 3-0 | 21-51-13 | D02974 | | X1 | | TB0163Z | 8 | BJ | | 001-099 |
| 6061 | 24 | GK | | | 9-0 | 21-51-13 | D02974 | | X2 | | D40060J | 17 | | | 001-099 |
| 6063 | 24 | GK | | | 9-0 | 21-51-13 | D02970 | | X2 | | D40060J | 6 | | | 001-099 |
| 6064 | 24 | GK | | | 3-0 | 21-51-13 | D02970 | | X1 | | TB0163Z | 8 | BJ | | 001-099 |
| 6065 | 22 | GK | | | 3-0 | 21-51-13 | D02950 | | C3 | | D02970 | A2 | | | 001-099 |
| 6066 | 24 | GK | | | 3-0 | 21-51-13 | D02970 | | A1 | | TB0163Z | 9 | BJ | | 001-099 |
| 6067 | 24 | GK | | | 3-0 | 21-51-13 | D02974 | | A1 | | TB0163Z | 9 | BJ | | 001-099 |
| 6068 | 22 | GK | | | 3-0 | 21-51-13 | D02950 | | A3 | | D02974 | A2 | | | 001-099 |
| 6069 | 24 | GK | | | 3-0 | 21-51-13 | D02950 | | D2 | | TB0163Z | 9 | BJ | | 001-099 |
| 6070 | 24 | GK | | | 3-0 | 21-51-13 | D40716J | | 18 | | SM00017 | | WI | | 001-099 |
| 6071 | 24 | GK | | | 4-0 | 21-51-13 | D40060J | | 29 | | SM00017 | | WI | | 001-099 |
| 6072 | 24 | GK | | | 9-0 | 21-51-13 | D02948 | | X2 | * | D40060J | 38 | | | 001-099 |
| 6073 | 22 | GK | | | 9-0 | 21-51-13 | D02948 | | A2 | | D40060J | 40 | | | 001-099 |
| 6074 | 22 | GK | | | 9-0 | 21-51-13 | D02948 | | B2 | | D40060J | 48 | | | 001-099 |
| 6075 | 24 | GK | | | 9-0 | 21-51-13 | D02976 | | X2 | | D40060J | 30 | | | 001-099 |
| 6076 | 24 | GK | | | 3-0 | 21-51-13 | D02976 | | X1 | | TB0163Z | 8 | BJ | | 001-099 |
| 6077 | 24 | GK | | | 12-0 | 21-51-13 | D02978 | | X2 | | D40060J | 35 | | | 001-099 |
| 6078 | 24 | GK | | | 12-0 | 21-51-13 | D02978 | | X1 | | TB0163Z | 8 | BJ | | 001-099 |
| 6079 | 24 | GK | | | 12-0 | 21-51-13 | D02980 | | X1 | | TB0163Z | 8 | BJ | | 001-099 |
| 6080 | 24 | GK | | | 12-0 | 21-51-13 | D02980 | | X2 | | D40060J | 37 | | | 001-099 |
| 6081 | 22 | GK | | | 3-0 | 21-51-13 | D02948 | | C3 | | D02976 | A2 | | | 001-099 |
| 6082 | 24 | GK | | | 3-0 | 21-51-13 | D02976 | | A1 | | TB0163Z | 9 | BJ | | 001-099 |
| 6083 | 22 | GK | | | 12-0 | 21-51-13 | D02948 | | B3 | | D02978 | A2 | | | 001-099 |
| 6084 | 24 | GK | | | 12-0 | 21-51-13 | D02978 | | A1 | | TB0163Z | 9 | BJ | | 001-099 |
| 6086 | 24 | GK | | | 12-0 | 21-51-13 | D02980 | | A1 | | TB0163Z | 9 | BJ | | 001-099 |
| 6087 | 22 | GK | | | 12-0 | 21-51-13 | D02948 | | A3 | | D02980 | A2 | | | 001-099 |
| 6088 | 24 | GK | | | 6-0 | 21-51-13 | D02948 | | D3 | | SM00017 | | WI | | 001-099 |
| 6089 | 24 | GK | | | 3-0 | 21-51-13 | D02948 | | D2 | | TB0163Z | 8 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 46

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 6090 | 24 | | GK | | 9-0 | 21-51-14 | D40060J | 51 | | | TB0163Z | 9 | BJ | | 001-099 |
| 6092 | 24 | | GK | | 12-0 | 21-51-14 | D04138 | 7 | | | TB0163Z | 8 | BJ | | 001-099 |
| 6093 | 24 | | GK | | 12-0 | 21-51-14 | D04138 | 3 | | | D40060J | 53 | | | 001-099 |
| 6094 | 24 | | GK | | 12-0 | 21-51-15 | D04052 | 11 | | | D40060J | 19 | | | 001-099 |
| 6095 | 24 | | GK | | 12-0 | 21-51-15 | D04052 | 7 | | | D40060J | 20 | | | 001-099 |
| 6096 | 24 | | GK | | 12-0 | 21-51-15 | D04052 | 8 | | | D40060J | 21 | | | 001-099 |
| 6097 | 24 | | GK | | 12-0 | 21-51-15 | D04052 | 10 | | | D40060J | 22 | | | 001-099 |
| 6098 | 22 | | GK | | 4-0 | 21-58-12 | D02596 | A1 | | | D05190 | A3 | | * | 001-099 |
| 6098 | 22 | | GK | | 3-0 | 21-58-12 | D02596 | A1 | | | D05190 | A3 | | * | 115-199 |
| 6102 | 24 | | GK | | 7-0 | 21-25-11 | D00572 | A3 | | | D41020J | 8 | | | ALL |
| 6147 | 22 | | GK | | 4-0 | 23-31-41 | D41497J | 55 | | | D40310J | 3 | | | 001-099 |
| 6147 | 22 | | GK | | 3-0 | 23-31-41 | D41497J | 55 | | | D40310J | 3 | | | 115-199 |
| 6149 | 22 | | GK | | 9-0 | 30-21-11 | D41850J | 48 | | | TB0161A | C004 | 2 | | ALL |
| 6150 | 22 | | GK | | 3-0 | 30-21-11 | TB0160Y | C018 | BJ | | D06326 | 8 | | | 001-099 |
| 6150 | 22 | | GK | | 4-0 | 30-21-11 | TB0160Y | A006 | BJ | | D06326 | 8 | | | 115-199 |
| 6195 | 22 | | GK | | 4-0 | 24-25-11 | D41850J | 25 | | | D40292J | 16 | | | 003-099 |
| 6196 | 22 | | GK | | 9-0 | 24-25-11 | D41850J | 52 | | | D04182 | X1 | | | 003-099 |
| 6198 | 20 | | GK | | 9-0 | 29-21-31 | D04706 | 3 | | | D41024J | 11 | | | 001-099 |
| 6198 | 20 | | GK | | 8-0 | 29-21-31 | D04706 | 3 | | | D41024J | 11 | | | 115-199 |
| 6199 | 20 | | GK | | 9-0 | 29-21-31 | D04706 | 5 | | | D41024J | 12 | | | 001-099 |
| 6199 | 20 | | GK | | 8-0 | 29-21-31 | D04706 | 5 | | | D41024J | 12 | | | 115-199 |
| 6200 | 20 | | GK | | 10-0 | 29-21-31 | D04706 | 4 | | | D41958J | 54 | | | 001-099 |
| 6200 | 20 | | GK | | 8-0 | 29-21-31 | D04706 | 4 | | | D41958J | 54 | | | 115-199 |
| 6201 | 22 | | GK | | 3-0 | 30-21-11 | D01504 | X1 | | * | D06326 | 3 | | | 001-099 |
| 6201 | 22 | | GK | | 4-0 | 30-21-11 | D06326 | 3 | | | D01504 | X1 | | * | 115-199 |
| 6202 | 22 | | GK | | 3-0 | 30-21-11 | D06326 | 6 | | | GD01674 | DC.. | 2 | | 001-099 |
| 6202 | 22 | | GK | | 4-0 | 30-21-11 | D06326 | 6 | | | GD01674 | DC.. | 2 | | 115-199 |
| 6204 | 22 | | GK | | 1-0 | 32-09-11 | TB0160A | A015 | 2 | | TB0160Y | C008 | BJ | | 115-199 |
| 6205 | 22 | | GK | | 8-0 | 23-34-15 | D01349 | X1 | | | D41497J | 47 | | | 001-099 |
| 6205 | 22 | | GK | | 6-0 | 23-34-15 | D01349 | X1 | | | SM00022 | | WI | | 115-199 |
| 6206 | 22 | | GK | | 8-0 | 23-34-15 | D01349 | X2 | | | D41497J | 46 | | | ALL |
| 6207 | 22 | | GK | | 4-0 | 23-34-15 | D01349 | B1 | | | GD01683 | AC.. | 2 | | ALL |
| 6208 | 22 | | GK | | 4-0 | 23-34-15 | D01349 | A1 | | | GD01683 | AC.. | 2 | | ALL |
| 6209 | 22 | | GK | | 8-0 | 23-34-15 | D01349 | B2 | | | D41497J | 48 | | | 001-099 |
| 6209 | 22 | | GK | | 6-0 | 23-34-15 | D01349 | B2 | | | SM00024 | | WI | | 115-199 |
| 6210 | 22 | | GK | | 8-0 | 23-34-15 | D01349 | A2 | | | D41497J | 49 | | | ALL |
| 6211 | 22 | | GK | | 8-0 | 23-34-15 | D01351 | X2 | | | D41497J | 52 | | | 115-199 |
| 6212 | 22 | | GK | | 6-0 | 23-34-15 | D01351 | X1 | | | SM00022 | | WI | | 115-199 |
| 6213 | 22 | | GK | | 4-0 | 23-34-15 | D01351 | A2 | | | GD01683 | AC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 47

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | | |
| 6215 | 22 | | GK | | 3-0 | 23-34-15 | D41497J | 47 | | | | SM00022 | | WI | | 115-199 |
| 6216 | 22 | | GK | | 3-0 | 23-34-15 | D41497J | 48 | | | | SM00024 | | WI | | 115-199 |
| 6224 | 22 | | GK | | 6-0 | 23-34-15 | D01351 | A1 | | | | SM00024 | | WI | | 115-199 |
| 6226 | 22 | | GK | | 3-0 | 32-09-11 | D00592 | X2 | | * | | TB0160Y | A020 | BJ | | 001-099 |
| 6227 | 24 | | GK | | 7-0 | 21-58-11 | TB0161A | C002 | 2 | | | SM00015 | | WI | | 001-099 |
| 6228 | 24 | | GK | | 5-0 | 21-58-11 | TB0161A | A001 | 2 | | | TB0161A | A002 | 2 | | 001-099 |
| 6229 | 24 | | GK | | 5-0 | 21-58-21 | TB0160A | C017 | 2 | | | TB0161A | C001 | 2 | | 001-099 |
| 6230 | 24 | | GK | | 5-0 | 21-58-21 | D04234 | 12 | | | | TB0160A | C017 | 2 | | 001-099 |
| 6243 | 22 | | GK | | 3-0 | 32-09-11 | D04184 | X1 | | * | | TB0160Z | 9 | BJ | | 001-099 |
| 6244 | 22 | | GK | | 1-0 | 32-09-11 | TB0160A | C028 | 2 | | | TB0160A | C029 | 2 | | ALL |
| 6246 | 22 | | PA | | 9-0 | 34-61-16 | D02275 | 7 | | | | D43019J | 2 | | | 115-199 |
| 6247 | 22 | | PA | | 9-0 | 34-61-16 | D02275 | 3 | | | | D43019J | 1 | | | 115-199 |
| 6249 | 22 | | PA | | 9-0 | 34-61-16 | D02279 | 7 | | | | D43019J | 19 | | | 115-199 |
| 6250 | 22 | | PA | | 9-0 | 34-61-16 | D02279 | 3 | | | | D43019J | 18 | | | 115-199 |
| 6252 | 22 | | PA | | 9-0 | 34-22-38 | D41493J | 21 | | | | D01515 | X2 | | | 115-199 |
| 6255 | 22 | | PA | | 7-0 | 34-22-38 | TB0163Y | A013 | BJ | | | D01515 | X1 | | | 115-199 |
| 6256 | 22 | | GA | | 7-0 | 34-22-16 | D41497J | 4 | | | | TB0163A | A011 | 2 | | 002 |
| 6256 | 22 | | PA | | 8-0 | 34-22-16 | TB0163Y | A013 | BJ | | | D41497J | 45 | | | 115-199 |
| 6290 | 22 | | GK | | 8-0 | 23-31-19 | D41497J | 28 | | | | TB0165A | C011 | 2 | | 001-099 |
| 6291 | 22 | | GK | | 4-0 | 23-31-19 | D01457 | 6 | | | | TB0165A | C011 | 2 | | 001-099 |
| 6292 | 22 | | GK | | 4-0 | 23-31-19 | D01457 | 12 | | | | TB0165A | A011 | 2 | | 001-099 |
| 6295 | 22 | | GK | | 8-0 | 23-31-19 | D41497J | 43 | | | | TB0165A | A011 | 2 | | 001-099 |
| 6297 | 22 | | GK | | 8-0 | 23-31-19 | D01457 | 9 | | | | D41497J | 40 | | | 001-099 |
| 6298 | 22 | | GK | | 8-0 | 23-31-19 | D01457 | 11 | | | | D41497J | 23 | | | 001-099 |
| 6299 | 22 | | GK | | 3-0 | 23-31-19 | D01457 | 10 | | | | GD01687 | DC.. | 2 | | 001-099 |
| 6311 | 20 | | GK | | 9-0 | 24-11-11 | D07046 | 1 | | | | D41850J | 49 | | | ALL |
| 6312 | 20 | | GK | | 9-0 | 24-11-11 | D07046 | 13 | | | | D40874J | 50 | | | ALL |
| 6329 | 22 | | GK | | 8-0 | 76-11-11 | TB0164A | A001 | 2 | | | D41248J | 1 | | | ALL |
| 6330 | 22 | | GK | | 8-0 | 76-11-11 | TB0164A | A002 | 2 | | | D41248J | 2 | | | ALL |
| 6331 | 22 | | GK | | 8-0 | 76-11-11 | TB0164A | C002 | 2 | | | D41248J | 3 | | | ALL |
| 6332 | 22 | | GK | | 8-0 | 76-11-11 | TB0164A | C001 | 2 | | | SM00048 | | WI | | ALL |
| 6333 | 22 | | GK | | 8-0 | 76-11-11 | TB0164A | C003 | 2 | | | D41958J | 29 | | | ALL |
| 6334 | 22 | | GK | | 1-0 | 76-11-11 | TB0164A | A003 | 2 | | | TB0164A | A002 | 2 | | ALL |
| 6335 | 22 | | GK | | 1-0 | 76-11-11 | TB0164A | A003 | 2 | | | TB0164A | A001 | 2 | | ALL |
| 6349 | 20 | | GK | | 6-0 | 38-13-11 | D40728J | 1 | | | | D41022J | 5 | | | 001-099 |
| 6350 | 22 | | GK | | 3-0 | 32-09-11 | D06914 | 6 | | | | TB0160Z | 23 | BJ | | ALL |
| 6351 | 22 | | GK | | 10-0 | 32-09-11 | D06914 | 12 | | | | TB0165A | A023 | 2 | | ALL |
| 6352 | 22 | | GK | | 10-0 | 32-09-11 | TB0160A | C024 | 2 | | | TB0165A | C023 | 2 | | 001-099 |
| 6352 | 22 | | GK | | 10-0 | 32-09-11 | TB0160A | C003 | 2 | | | TB0165A | C023 | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 48

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 6379 | 24 | | GK | | 2-0 | 24-25-13 | D40292J | | 10 | | D41475J | 46 | | | 003-099 |
| 6381 | 22 | | GK | | 8-0 | 24-25-11 | D40292J | | 12 | | TB0161Y | A018 | BJ | | 003-099 |
| 6382 | 22 | | GK | | 8-0 | 24-25-11 | TB0161Y | A018 | BJ | | D41024J | 9 | | | 003-099 |
| 6392 | 22 | | GK | | 3-0 | 32-61-11 | D40716J | | 4 | | D41022J | 10 | | | 001-002, 115-199 |
| 6392 | 22 | | GK | | 3-0 | 32-61-11 | D40728J | | 14 | | D41024J | 31 | | | 003-099 |
| 6402 | 20 | | GK | | 2-0 | 21-45-11 | D00594 | | D3 | | GD01670 | AC.. | 2 | | 003-009 |
| 6405 | 24 | | GK | | 7-0 | 78-36-11 | D07718 | | 3 | | SM00040 | | WI | | 001-002 |
| 6405 | 24 | | GK | | 6-0 | 78-36-11 | D07718 | | 3 | | SM00040 | | WI | | 003-099 |
| 6405 | 24 | | GK | | 6-0 | 78-36-11 | SM00040 | | | WI | D07718 | 3 | | | 115-199 |
| 6406 | 24 | | GK | | 7-0 | 78-36-11 | D07718 | | 7 | | TB0166Y | C006 | BJ | | 001-002 |
| 6406 | 24 | | GK | | 6-0 | 78-36-11 | D07718 | | 7 | | SM00038 | | WI | | 003-099 |
| 6406 | 24 | | GK | | 9-0 | 78-36-11 | TB0165Y | A019 | BJ | | D07718 | 7 | | | 115-199 |
| 6407 | 22 | | GK | | 10-0 | 32-09-11 | D00592 | X2 | | * | TB0360B | A015 | 2 | | 003-099 |
| 6412 | 24 | | GK | | 4-0 | 78-36-11 | D41462J | | 22 | | SM00040 | | WI | | ALL |
| 6413 | 24 | | GK | | 7-0 | 78-36-11 | D07718 | | 5 | | SM00040 | | WI | | 001-002 |
| 6413 | 24 | | GK | | 6-0 | 78-36-11 | D07718 | | 5 | | SM00040 | | WI | | 003-099 |
| 6413 | 24 | | GK | | 6-0 | 78-36-11 | SM00040 | | | WI | D07718 | 5 | | | 115-199 |
| 6425 | 22 | | GA | | 4-0 | 27-62-11 | TB0166C | A030 | 2 | | TB0166B | A031 | 2 | | 010-099 |
| 6426 | 22 | | GA | | 8-0 | 27-62-11 | D03194 | B1 | | * | TB0166B | C031 | 2 | | 010-099 |
| 6437 | 22 | | GA | | 4-0 | 31-31-61 | D41473J | | 10 | | TB0166C | C030 | 2 | | 010-099 |
| 6446 | 22 | | GK | | 9-0 | 78-34-11 | D41462J | | 17 | | M10004 | A | C | | 001-002 |
| 6446 | 22 | | GK | | 7-0 | 78-34-11 | D41462J | | 17 | | M10004 | A | C | | 115-199 |
| 6451 | 22 | | GK | | 9-0 | 78-34-11 | M10004 | B | C | | TB0163Z | 6 | BJ | | 001-002 |
| 6451 | 22 | | GK | | 8-0 | 78-34-11 | TB0165Y | A018 | BJ | | M10004 | B | C | | 003-099 |
| 6451 | 22 | | GK | | 9-0 | 78-34-11 | M10004 | B | C | | TB0165Y | A018 | BJ | | 115-199 |
| 6452 | 20 | | GK | | 6-0 | 78-34-11 | D41462J | | 18 | | GD03600 | ST.. | 2 | | 001-002 |
| 6452 | 20 | | GK | | 5-0 | 78-34-11 | D41462J | | 18 | | GD03600 | ST.. | 2 | | 003-099, 115-199 |
| 6453 | 18 | | GK | | 9-0 | 78-34-51 | D41462J | | 19 | 18 | SM00042 | | WI | | 001-002 |
| 6453 | 18 | | GK | | 8-0 | 78-34-51 | D41462J | | 19 | 18 | TB0161G | 30 | 2 | | 003-099 |
| 6453 | 18 | | GK | | 4-0 | 78-34-51 | D41462J | | 19 | 18 | SM00042 | | WI | | 115-199 |
| 6454 | 20 | | GK | | 9-0 | 78-34-51 | D41948J | | 51 | | SM00042 | | WI | | 001-002 |
| 6454 | 20 | | GK | | 9-0 | 78-34-51 | D41948J | | 6 | | TB0161G | 30 | 2 | | 003-099 |
| 6454 | 20 | | GK | | 2-0 | 78-34-51 | D41948J | | 51 | | SM00042 | | WI | | 115-199 |
| 6455 | 20 | | GK | | 3-0 | 78-34-51 | SM00042 | | | WI | D01782 | 10 | | | 001-002, 115-199 |
| 6455 | 20 | | GK | | 3-0 | 78-34-51 | TB0161G | | 30 | 2 | D01782 | 10 | | | 003-099 |
| 6456 | 20 | | GK | | 3-0 | 78-34-51 | TB0161C | A029 | 2 | | GD01672 | DC.. | 2 | | 001-002, 115-199 |
| 6456 | 20 | | GK | | 4-0 | 78-34-51 | TB0161C | A029 | 2 | | GD01672 | DC.. | 2 | | 003-099 |
| 6457 | 20 | | GK | | 3-0 | 78-34-51 | D07776 | X2 | | | GD01672 | DC.. | 2 | | 001-099 |
| 6457 | 20 | | GK | | 4-0 | 78-34-51 | GD01672 | DC.. | 2 | | D07776 | X2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 49

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 6458 | 24 | | GK | | 9-0 | 78-36-11 | D41958J | | 8 | | D07718 | | 2 | | 001-002 |
| 6458 | 24 | | GK | | 9-0 | 78-36-11 | D07718 | | 2 | | D41958J | | 8 | | 003-099 |
| 6458 | 24 | | GK | | 8-0 | 78-36-11 | D41958J | | 8 | | D07718 | | 2 | | 115-199 |
| 6487 | 22 | | GK | | 10-0 | 76-11-11 | D02154 | | 3 | | SM00048 | | | WI | 001-099 |
| 6487 | 22 | | GK | | 8-0 | 76-11-11 | D02154 | | 3 | | SM00048 | | | WI | 115-199 |
| 6488 | 22 | | GK | | 4-0 | 76-11-11 | SM00047 | | | WI | D02154 | | 8 | | 115-199 |
| 6489 | 22 | | GK | | 4-0 | 76-11-11 | SM00047 | | | WI | D02158 | | 3 | | 115-199 |
| 6490 | 22 | | GK | | 8-0 | 76-11-11 | D41248J | | 4 | | SM00048 | | | WI | ALL |
| 6491 | 24 | | GK | | 3-0 | 36-11-41 | D07036 | | A3 | | D05258 | | B3 | | 010-099 |
| 6506 | 24 | | GK | | 10-0 | 21-25-11 | D40910J | | 26 | | TB0161A | | C010 | 2 | 001-099 |
| 6506 | 24 | | GK | | 10-0 | 21-25-11 | TB0161A | | C010 | 2 | D40910J | | 26 | | 115-199 |
| 6526 | 24 | | GK | | 12-0 | 78-36-11 | D41958J | | 27 | | D02746 | | B2 | | * 001-099 |
| 6526 | 24 | | GK | | 12-0 | 78-36-11 | D41958J | | 42 | | D02746 | | B2 | | * 115-199 |
| 6527 | 24 | | GK | | 12-0 | 78-36-11 | D02746 | | B2 | * | D01784 | | 3 | | ALL |
| 6528 | 24 | | GK | | 12-0 | 78-36-11 | D02746 | | B3 | | D01784 | | 4 | | ALL |
| 6530 | 24 | | GK | | 12-0 | 78-36-11 | D01784 | | 5 | | D41958J | | 30 | | ALL |
| 6614 | 24 | | GK | | 4-0 | 76-11-11 | TB0165B | | C024 | 2 | GD01687 | | DC.. | 2 | ALL |
| 6615 | 24 | | GK | | 4-0 | 76-11-11 | TB0166Y | | A019 | BJ | TB0165B | | A024 | 2 | 001-099 |
| 6616 | 24 | | GK | | 4-0 | 76-11-11 | TB0165Y | | C014 | BJ | TB0165B | | A024 | 2 | 115-199 |
| 8002 | 22 | | GK | | 7-0 | 34-61-15 | D02524 | | X1 | | D41475J | | 32 | | ALL |
| 8003 | 22 | | GK | | 2-0 | 34-61-15 | D02524 | | X2 | | GD01693 | | DC.. | 2 | 001-099 |
| 8003 | 22 | | GK | | 10-0 | 34-61-15 | D02524 | | X2 | | D41475J | | 33 | | 115-199 |
| 8004 | 24 | | GK | | 5-0 | 26-16-21 | D40716J | | 5 | | TB0163Y | | A020 | BJ | 115-199 |
| 8005 | 24 | | GK | | 6-0 | 26-16-21 | D04440 | | A2 | * | D40716J | | 5 | | 001-099 |
| 8005 | 24 | | GK | | 3-0 | 26-16-21 | D04440 | | A2 | | TB0163Y | | A020 | BJ | 115-199 |
| 8006 | 24 | | GK | | 5-0 | 26-16-21 | D40716J | | 16 | | TB0163Y | | A024 | BJ | 115-199 |
| 8007 | 24 | | GK | | 1-0 | 26-16-21 | D04438 | | A2 | | D04440 | | A2 | | * 001-099 |
| 8007 | 24 | | GK | | 3-0 | 26-16-21 | D04438 | | A2 | | TB0163Y | | A020 | BJ | 115-199 |
| 8008 | 24 | | GK | | 6-0 | 26-16-21 | D04440 | | X1 | * | D40716J | | 16 | | 001-099 |
| 8008 | 24 | | GK | | 3-0 | 26-16-21 | D04440 | | X1 | | TB0163Y | | A024 | BJ | 115-199 |
| 8009 | 24 | | GK | | 1-0 | 26-16-21 | D04438 | | X1 | | D04440 | | X1 | | * 001-099 |
| 8009 | 24 | | GK | | 3-0 | 26-16-21 | D04438 | | X1 | | TB0163Y | | A024 | BJ | 115-199 |
| 8010 | 22 | | GK | | 2-0 | 26-16-21 | D04438 | | B2 | | GD01693 | | DC.. | 2 | 001-099 |
| 8010 | 22 | | GK | | 3-0 | 26-16-21 | D04438 | | B2 | | GD01693 | | DC.. | 2 | 115-199 |
| 8011 | 24 | | GK | | 1-0 | 26-16-21 | D04438 | | B1 | * | D04438 | | X2 | | * 001-099 |
| 8011 | 24 | | GK | | 3-0 | 26-16-21 | D04438 | | B1 | | TB0163Y | | C019 | BJ | 115-199 |
| 8012 | 24 | | GK | | 2-0 | 26-16-21 | TB0163B | | A002 | 2 | D04438 | | B1 | | * 001-099 |
| 8012 | 24 | | GK | | 2-0 | 26-16-21 | TB0163B | | A028 | 2 | TB0163Y | | C019 | BJ | 115-199 |
| 8013 | 24 | | GK | | 7-0 | 26-16-21 | D04438 | | X2 | * | D41497J | | 32 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 50

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 8013 | 24 | | GK | | 3-0 | 26-16-21 | D04438 | | X2 | | TB0163Y | C019 | BJ | | 115-199 |
| 8014 | 24 | | GK | | 6-0 | 26-16-21 | D04438 | | A3 | | D40728J | 19 | | | ALL |
| 8015 | 24 | | GK | | 6-0 | 26-16-21 | D40728J | | 20 | | D04438 | A1 | | | ALL |
| 8016 | 24 | | GK | | 6-0 | 26-16-21 | D40728J | | 30 | | TB0163B | C002 | 2 | | 001-099 |
| 8016 | 24 | | GK | | 7-0 | 26-16-21 | D40728J | | 30 | | TB0163B | C028 | 2 | | 115-199 |
| 8017 | 24 | | GK | | 6-0 | 26-16-21 | TB0163Y | C019 | BJ | | D41497J | 32 | | | 115-199 |
| 8018 | 24 | | GK | | 7-0 | 26-16-21 | D04440 | | B1 | * | D41497J | 33 | | | 001-099 |
| 8018 | 24 | | GK | | 6-0 | 26-16-21 | TB0163Y | C020 | BJ | | D41497J | 33 | | | 115-199 |
| 8019 | 24 | | GK | | 2-0 | 26-16-21 | TB0163B | C017 | 2 | | TB0163B | C002 | 2 | | 001-099 |
| 8019 | 24 | | GK | | 2-0 | 26-16-21 | TB0163B | C026 | 2 | | TB0163B | C028 | 2 | | 115-199 |
| 8020 | 24 | | GK | | 2-0 | 26-16-21 | TB0163B | C016 | 2 | | TB0163B | C001 | 2 | | 001-099 |
| 8020 | 24 | | GK | | 2-0 | 26-16-21 | TB0163B | C025 | 2 | | TB0163B | C027 | 2 | | 115-199 |
| 8021 | 24 | | GK | | 6-0 | 26-16-21 | TB0163B | C016 | 2 | | D40728J | 31 | | | 001-099 |
| 8021 | 24 | | GK | | 7-0 | 26-16-21 | TB0163B | C025 | 2 | | D40728J | 31 | | | 115-199 |
| 8022 | 22 | | GK | | 2-0 | 26-16-21 | D04440 | | B2 | | GD01693 | DC.. | 2 | | 001-099 |
| 8022 | 22 | | GK | | 5-0 | 26-16-21 | D04440 | | B2 | | GD01693 | DC.. | 2 | | 115-199 |
| 8023 | 24 | | GK | | 1-0 | 26-16-21 | D04440 | | B1 | * | D04440 | X2 | | * | 001-099 |
| 8023 | 24 | | GK | | 3-0 | 26-16-21 | D04440 | | B1 | | TB0163Y | C020 | BJ | | 115-199 |
| 8024 | 24 | | GK | | 2-0 | 26-16-21 | D04440 | | X2 | * | TB0163B | A016 | 2 | | 001-099 |
| 8024 | 24 | | GK | | 3-0 | 26-16-21 | D04440 | | X2 | | TB0163Y | C020 | BJ | | 115-199 |
| 8025 | 24 | | GK | | 2-0 | 26-16-21 | TB0163B | A025 | 2 | | TB0163Y | C020 | BJ | | 115-199 |
| 8026 | 24 | | GK | | 6-0 | 26-16-21 | TB0163B | A017 | 2 | | D41497J | 34 | | | 001-099 |
| 8026 | 24 | | GK | | 6-0 | 26-16-21 | TB0163B | A026 | 2 | | D41497J | 34 | | | 115-199 |
| 8027 | 24 | | GK | | 1-0 | 26-16-21 | TB0163B | A017 | 2 | | TB0163B | A001 | 2 | | 001-099 |
| 8027 | 24 | | GK | | 2-0 | 26-16-21 | TB0163B | A026 | 2 | | TB0163B | A027 | 2 | | 115-199 |
| 8028 | 24 | | GK | | 6-0 | 26-16-21 | D04440 | | A3 | | D40728J | 10 | | | 001-099 |
| 8028 | 24 | | GK | | 7-0 | 26-16-21 | D04440 | | A3 | | D40728J | 10 | | | 115-199 |
| 8029 | 24 | | GK | | 6-0 | 26-16-21 | D04440 | | A1 | | D40728J | 22 | | | 001-099 |
| 8029 | 24 | | GK | | 7-0 | 26-16-21 | D04440 | | A1 | | D40728J | 22 | | | 115-199 |
| 8030 | 22 | | GK | | 6-0 | 30-34-21 | D05522 | | A3 | | D40582J | 29 | | | 001-099 |
| 8030 | 22 | | GK | | 7-0 | 30-34-21 | D40582J | | 36 | | D05522 | A3 | | | 115-199 |
| 8031 | 22 | | GK | | 2-0 | 30-34-21 | D05522 | | C3 | | GD02867 | DC.. | 2 | | 001-099 |
| 8031 | 22 | | GK | | 3-0 | 30-34-21 | D05522 | | C3 | | GD02867 | DC.. | 2 | | 115-199 |
| 8032 | 22 | | GK | | 7-0 | 30-34-21 | D05522 | | D2 | | D41475J | 36 | | | 001-099 |
| 8032 | 22 | | GK | | 7-0 | 30-34-21 | D41475J | | 36 | | D05522 | D2 | | | 115-199 |
| 8033 | 22 | | GK | | 2-0 | 30-34-21 | D05522 | | B2 | | GD02867 | DC.. | 2 | | 001-099 |
| 8033 | 22 | | GK | | 3-0 | 30-34-21 | D05522 | | B2 | | GD02867 | DC.. | 2 | | 115-199 |
| 8034 | 22 | | GK | | 7-0 | 30-34-21 | D05522 | | D3 | | D41475J | 37 | | | 001-099 |
| 8034 | 22 | | GK | | 7-0 | 30-34-21 | D41475J | | 37 | | D05522 | D3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 51

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1260 | 286N1260 | | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | | |
| 8035 | 22 | | GK | | 6-0 | 30-34-21 | | D05522 | | X1 | | D40696J | 30 | | | 001-099 | |
| 8035 | 22 | | GK | | 7-0 | 30-34-21 | | D40696J | | 30 | | D05522 | X1 | | | 115-199 | |
| 8036 | 22 | | GK | | 2-0 | 30-34-21 | | D05522 | | X2 | | GD02867 | DC.. | 2 | | 001-099 | |
| 8036 | 22 | | GK | | 3-0 | 30-34-21 | | D05522 | | X2 | | GD02867 | DC.. | 2 | | 115-199 | |
| 8037 | 18 | | GK | | 6-0 | 30-34-21 | | D05522 | | C1 | | D41938J | 18 | 18 | | 001-099 | |
| 8037 | 18 | | GK | | 7-0 | 30-34-21 | | D41938J | 18 | 18 | | D05522 | C1 | | | 115-199 | |
| 8038 | 18 | | GK | | 3-0 | 30-34-21 | | D05522 | | B1 | | GD01693 | AC.. | 2 | | 001-099 | |
| 8038 | 18 | | GK | | 3-0 | 30-34-21 | | D05522 | | B1 | | GD02867 | AC.. | 2 | | 115-199 | |
| 8075 | 24 | | GK | | 2-0 | 21-58-12 | | D05626 | | X2 | | GD01693 | DC.. | 2 | | 001-099 | |
| 8075 | 24 | | GK | | 3-0 | 21-58-12 | | D05626 | | X2 | | GD01693 | DC.. | 2 | | 115-199 | |
| 8077 | 24 | | GK | | 2-0 | 21-58-12 | | D05626 | | A2 | | GD01693 | DC.. | 2 | | 001-099 | |
| 8077 | 24 | | GK | | 3-0 | 21-58-12 | | D05626 | | A2 | | GD01693 | DC.. | 2 | | 115-199 | |
| 8083 | 24 | | GK | | 4-0 | 21-58-12 | | D05626 | | A1 | | SM00015 | | WI | | ALL | |
| 8090 | 24 | | GK | | 5-0 | 21-58-12 | | D05626 | | X1 | | D41022J | 11 | | | 001-099 | |
| 8090 | 24 | | GK | | 8-0 | 21-58-12 | | D05626 | | X1 | | D41022J | 11 | | | 115-199 | |
| 8095 | 20 | | GK | | 3-0 | 24-31-11 | | D40914J | | 8 | | D40292J | 11 | | | 003-099 | |
| 8299 | 20 | | GK | | 7-0 | 27-62-11 | | D41020J | | 17 | | TB0160Z | 9 | BJ | | ALL | |
| 8500 | 22 | | GK | | 4-0 | 29-22-11 | | D41948J | | 55 | | D41850J | 18 | | | ALL | |
| 8501 | 22 | | GK | | 4-0 | 29-22-11 | | D41948J | | 54 | | D41850J | 19 | | | ALL | |
| 8502 | 22 | | GK | | 4-0 | 29-22-11 | | D41948J | | 53 | | D41850J | 20 | | | ALL | |
| 8507 | 22 | | GK | | 6-0 | 27-09-12 | | TB0160Y | A018 | BJ | | D41493J | 17 | | | 001-099 | |
| 8507 | 22 | | GK | | 7-0 | 27-09-12 | | TB0161Y | C024 | BJ | | D41493J | 17 | | | 115-199 | |
| 8508 | 22 | | GK | | 6-0 | 27-09-12 | | TB0160Y | A018 | BJ | | D41493J | 18 | | | 001-099 | |
| 8508 | 22 | | GK | | 7-0 | 27-09-12 | | TB0161Y | C024 | BJ | | D41493J | 18 | | | 115-199 | |
| 8510 | 22 | | GK | | 8-0 | 29-11-22 | | M10559 | A | C | | D41690J | 2 | | | 001-099 | |
| 8510 | 22 | | GK | | 9-0 | 29-11-22 | | M10559 | A | C | | D41690J | 2 | | | 115-199 | |
| 8511 | 22 | | GK | | 8-0 | 29-11-22 | | M10559 | B | C | | D41690J | 1 | | | 001-099 | |
| 8511 | 22 | | GK | | 9-0 | 29-11-22 | | M10559 | B | C | | D41690J | 1 | | | 115-199 | |
| 8512 | 22 | | GK | | 6-0 | 29-11-22 | | M10560 | B | C | | D42096J | 3 | | | 001-099 | |
| 8512 | 22 | | GK | | 9-0 | 29-11-22 | | M10560 | B | C | | D42096J | 3 | | | 115-199 | |
| 8514 | 22 | | GK | | 8-0 | 29-11-22 | | M10560 | A | C | | D41690J | 3 | | | 001-099 | |
| 8514 | 22 | | GK | | 9-0 | 29-11-22 | | M10560 | A | C | | D42096J | 6 | | | 115-199 | |
| 8515 | 24 | | GK | | 5-0 | 29-33-11 | | D41022J | 37 | | | TB0168A | A010 | 2 | | 001-099 | |
| 8515 | 24 | | GK | | 6-0 | 29-33-11 | | D41022J | 37 | | | TB0362C | A003 | 2 | | 115-199 | |
| 8516 | 24 | | GK | | 7-0 | 29-33-11 | | D40608J | 30 | | | TB0168A | C013 | 2 | | 001-099 | |
| 8516 | 24 | | GK | | 9-0 | 29-33-11 | | D42080J | 6 | | | TB0362C | C001 | 2 | | 115-199 | |
| 8517 | 24 | | GK | | 7-0 | 29-33-11 | | D41958J | 41 | | | TB0168A | C009 | 2 | | 001-099 | |
| 8517 | 24 | | GK | | 9-0 | 29-33-11 | | D41958J | 41 | | | TB0362C | C002 | 2 | | 115-199 | |
| 8518 | 24 | | GK | | 5-0 | 29-33-11 | | D41612J | 10 | | | TB0168A | C010 | 2 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 52

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1260 | 286N1260 | | | INTERNAL P36- PLATES (A,B,D,E,F) (continued) | | | | | | | | | | | |
| 8518 | 24 | | GK | | 7-0 | 29-33-11 | D40728J | | 37 | | TB0362C | C003 | 2 | | 115-199 |
| 8519 | 20 | | GK | | 3-0 | 33-42-12 | D40582J | | 40 | | D40390J | | 4 | | 001-099 |
| 8522 | 20 | | GK | | 3-0 | 33-42-31 | D40910J | | 19 | | D40390J | | 7 | | 001-099 |
| 8525 | 22 | | GK | | 5-0 | 29-11-31 | D40542J | | 6 | | TB0168Y | A003 | BJ | | 115-199 |
| 8531 | 18 | | GK | | 7-0 | 30-34-21 | TB0160G | | 7 | 2 | D40696J | | 27 | 18 | 001-099 |
| 8531 | 18 | | GK | | 8-0 | 30-34-21 | D40696J | | 50 | 18 | TB0161G | | 6 | 2 | 115-199 |
| 8535 | 18 | | GK | | 7-0 | 30-34-21 | TB0160G | | 8 | 2 | D41938J | | 17 | 18 | 001-099 |
| 8535 | 18 | | GK | | 8-0 | 30-34-21 | D41938J | | 17 | 18 | TB0161G | | 5 | 2 | 115-199 |
| 8536 | 22 | | GK | | 3-0 | 30-34-21 | D40582J | | 38 | | D41475J | | 35 | | 001-099 |
| 8536 | 22 | | GK | | 4-0 | 30-34-21 | D41475J | | 35 | | D40582J | | 38 | | 115-199 |
| 8543 | 22 | | GK | | 7-0 | 29-11-31 | D40608J | | 19 | | M10482 | A | C | | 001-099 |
| 8543 | 22 | | GK | | 8-0 | 29-11-31 | D40608J | | 19 | | M10482 | A | C | | 115-199 |
| 8552 | 24 | | GK | | 8-0 | 21-25-11 | D05501 | | 3 | | D41850J | | 41 | | ALL |
| 8554 | 22 | | GK | | 5-0 | 29-11-22 | M10560 | | B | C | D40582J | | 4 | | 001-099 |
| 8554 | 22 | | GK | | 8-0 | 29-11-22 | M10560 | | B | C | D40582J | | 4 | | 115-199 |
| 8907 | 20 | | GK | | 0-18 | 30-34-21 | D41938J | | 19 | | GD03600 | ST.. | 2 | | 001-099 |
| 8907 | 20 | | GK | | 2-0 | 30-34-21 | D41938J | | 19 | | GD03600 | ST.. | 2 | | 115-199 |
| C-01 | | | | | 0-0 | 27-58-11 | TS5084 | | 1 | | TB0165Y | C008 | BJ | | 001-099 |
| C-01 | | | | | 0-0 | 27-58-11 | TS5084 | | 1 | | TB0166Y | C004 | BJ | | 115-199 |
| C-02 | | | | | 0-0 | 27-58-11 | TS5084 | | 2 | | TB0165Y | A008 | BJ | | 001-099 |
| C-02 | | | | | 0-0 | 27-58-11 | TS5084 | | 2 | | TB0166Y | A004 | BJ | | 115-199 |
| C-03 | | | | | 0-0 | 27-58-11 | TS5084 | | 3 | | TB0165Y | A009 | BJ | | 001-099 |
| C-03 | | | | | 0-0 | 27-58-11 | TS5084 | | 3 | | TB0166Y | C001 | BJ | | 115-199 |
| C-04 | | | | | 0-0 | 27-58-11 | TS5084 | | 4 | | GD01683 | AC.. | 2 | | ALL |
| FRAG | | | | | 0-0 | 78-34-51 | D41462J | | | AG | D41462J | | 6 | | ALL |
| W1265 | 286N1265 | | | E3-1 SHELF | | | | | | | | | | | |
| 0001 | 22 | | GA | | 3-0 | 27-09-12 | TB0109Z | | 7 | BJ | D00709A | D07 | | | ALL |
| 0002 | 22 | | GA | | 3-8 | 27-09-12 | TB0109Z | | 7 | BJ | D41301J | | 25 | | ALL |
| 0003 | 22 | | GA | | 2-8 | 27-09-12 | TB0109Z | | 7 | BJ | D41775J | | 12 | | ALL |
| 0004 | 22 | | GA | | 4-2 | 27-09-12 | TB0109Z | | 7 | BJ | D00349A | H04 | | | ALL |
| 0005 | 22 | | GA | | 3-8 | 27-09-12 | TB0109Z | | 7 | BJ | D00705A | D06 | | | ALL |
| 0006 | 22 | | GA | | 4-5 | 27-09-12 | TB0109Z | | 7 | BJ | D00639B | D10 | | | ALL |
| 0008 | 22 | | GA | | 2-9 | 27-09-12 | TB0109Z | | 7 | BJ | D00635A | D01 | | | ALL |
| 0009 | 22 | | GA | | 2-8 | 27-09-13 | TB0109Y | | C006 | BJ | D41775J | | 14 | | ALL |
| 0010 | 22 | | GA | | 2-8 | 27-09-13 | TB0109Y | | A006 | BJ | D41775J | | 13 | | ALL |
| 0011 | 22 | | GA | | 3-8 | 27-09-13 | TB0109Y | | A006 | BJ | D41301J | | 23 | | ALL |
| 0012 | 22 | | GA | | 3-8 | 27-09-13 | TB0109Y | | C006 | BJ | D41301J | | 24 | | ALL |
| 0013 | 22 | | GA | | 3-7 | 27-09-13 | TB0109Y | | A006 | BJ | D00705B | F06 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 53

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | | 286N1265 | | | | E3-1 SHELF (continued) | | | | | | | | | |
| 0014 | 22 | GA | | | 3-7 | 27-09-13 | TB0109Y | C006 | BJ | | D00705B | F05 | | | ALL |
| 0015 | 22 | GA | | | 4-7 | 27-09-13 | TB0109Y | A006 | BJ | | D00639A | K13 | | | ALL |
| 0016 | 22 | GA | | | 4-7 | 27-09-13 | TB0109Y | C006 | BJ | | D00639A | J13 | | | ALL |
| 0017 | 22 | GA | | | 2-7 | 27-21-12 | D00701A | A08 | | | D00709A | A01 | | | ALL |
| 0018 | 22 | GA | | | 2-7 | 27-21-12 | D00701A | G03 | | | D00709A | D01 | | | ALL |
| 0019 | 22 | GA | | | 3-10 | 27-21-12 | D00703A | A08 | | | D00709A | A02 | | | ALL |
| 0020 | 22 | GA | | | 3-10 | 27-21-12 | D00703A | G03 | | | D00709A | D02 | | | ALL |
| 0025 | 22 | GA | | | 3-7 | 27-31-12 | D00705B | A01 | | | TB0109Y | A001 | BJ | | ALL |
| 0026 | 22 | GA | | | 3-7 | 27-31-12 | D00705B | B01 | | | TB0109Y | A001 | BJ | | ALL |
| 0027 | 22 | GA | | | 3-7 | 27-31-12 | D00705B | A04 | | | TB0109A | A021 | 2 | | ALL |
| 0028 | 22 | GA | | | 3-7 | 27-31-12 | TB0109A | A019 | 2 | | D00705B | A03 | | | ALL |
| 0029 | 20 | GA | | | 4-1 | 27-31-12 | TB0109A | C021 | 2 | | D41841J | 1 | | | ALL |
| 0030 | 20 | GA | | | 4-1 | 27-31-12 | TB0109A | C019 | 2 | | D41841J | 2 | | | ALL |
| 0031 | 20 | GA | | | 2-8 | 27-31-12 | TB0109Y | A001 | BJ | | D41775J | 21 | | | ALL |
| 0032 | 20 | GA | | | 2-8 | 27-31-12 | D41775J | 22 | | | TB0109A | A021 | 2 | | ALL |
| 0033 | 20 | GA | | | 2-8 | 27-31-12 | TB0109A | A019 | 2 | | D41775J | 31 | | | ALL |
| 0034 | 22 | GA | | | 3-5 | 27-31-12 | D00705A | E07 | | | D41775J | 36 | | | ALL |
| 0035 | 22 | GA | | | 3-5 | 27-31-12 | D00705A | E08 | | | D41775J | 37 | | | ALL |
| 0036 | 22 | GA | | | 2-4 | 27-61-13 | D00701A | A05 | | | D00635A | E11 | | | ALL |
| 0037 | 22 | GA | | | 2-4 | 27-61-13 | D00701A | H01 | | | D00635A | G03 | | | ALL |
| 0038 | 22 | GA | | | 2-4 | 27-61-13 | D00701A | C07 | | | D00635A | G05 | | | ALL |
| 0041 | 22 | GA | | | 4-1 | 27-61-13 | D00703A | C07 | | | D00635A | F05 | | | ALL |
| 0042 | 22 | GA | | | 4-1 | 27-61-13 | D00703A | H01 | | | D00635A | F03 | | | ALL |
| 0043 | 22 | GA | | | 4-1 | 27-61-13 | D00703A | A05 | | | D00635A | E12 | | | ALL |
| 0044 | 22 | GA | | | 2-9 | 27-61-17 | D00701A | H02 | | | D00637B | G04 | | | ALL |
| 0045 | 22 | GA | | | 2-9 | 27-61-17 | D00701A | C08 | | | D00637B | G06 | | | ALL |
| 0047 | 22 | GA | | | 3-5 | 27-61-17 | D00703A | H02 | | | D00637B | F04 | | | ALL |
| 0048 | 22 | GA | | | 3-5 | 27-61-17 | D00703A | C08 | | | D00637B | F06 | | | ALL |
| 0050 | 22 | GA | | | 4-5 | 27-61-17 | D00701A | C03 | | | D00703A | A03 | | | ALL |
| 0051 | 22 | GA | | | 4-10 | 27-61-17 | TB0109Z | 9 | BJ | | D00703A | C01 | | | ALL |
| 0053 | 22 | GA | | | 4-1 | 27-61-18 | D00701A | B07 | | | D00639B | G14 | | | ALL |
| 0054 | 22 | GA | | | 4-1 | 27-61-18 | D00701A | H03 | | | D00639B | G12 | | | ALL |
| 0055 | 22 | GA | | | 3-3 | 27-61-18 | D41301J | 10 | | | D00639B | H12 | | | ALL |
| 0056 | 22 | GA | | | 2-1 | 27-61-18 | D00703A | B07 | | | D00639B | F14 | | | ALL |
| 0057 | 22 | GA | | | 2-1 | 27-61-18 | D00703A | H03 | | | D00639B | F12 | | | ALL |
| 0058 | 22 | GA | | | 2-10 | 27-61-18 | D41301J | 11 | | | GD01986 | DC.. | 2 | | ALL |
| 0059 | 22 | GA | | | 2-6 | 22-22-11 | D41301J | 8 | | | D00705A | D09 | | | ALL |
| 0060 | 22 | GA | | | 2-6 | 22-22-11 | D41301J | 9 | | | D00705A | D10 | | | ALL |
| 0061 | 22 | GA | | | 3-5 | 22-22-11 | D41775J | 8 | | | D00705A | G12 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 54

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 0063 | 22 | | GA | | 3-5 | 22-24-11 | D41775J | | 3 | | D00705A | F11 | | | ALL |
| 0064 | 22 | | GA | | 3-5 | 22-24-11 | D41775J | | 4 | | D00705A | E11 | | | ALL |
| 0065 | 22 | | GA | | 2-8 | 27-41-31 | D41775J | | 6 | | TB0109Y | A014 | BJ | | ALL |
| 0066 | 22 | | GA | | 3-5 | 27-41-31 | D41709J | | 5 | | TB0109A | C028 | 2 | | 001-099 |
| 0066 | 22 | | GA | | 3-11 | 27-41-31 | D41709J | | 5 | | TB0109Y | A014 | BJ | | 115-199 |
| 0067 | 22 | | GA | | 3-8 | 27-41-31 | D00705A | | B06 | | TB0109Y | A014 | BJ | | ALL |
| 0068 | 22 | | GA | | 2-8 | 22-24-11 | D41775J | | 5 | | TB0109Y | C012 | BJ | | ALL |
| 0069 | 22 | | GA | | 3-8 | 22-24-11 | D41301J | | 36 | | TB0109Y | C012 | BJ | | ALL |
| 0070 | 22 | | GA | | 3-8 | 22-24-11 | D00705A | | A06 | | TB0109Y | C012 | BJ | | ALL |
| 0072 | 22 | | GA | | 2-5 | 27-41-31 | TB0109Y | | A014 | BJ | TB0109A | A028 | 2 | | 001-099 |
| 0073 | 22 | | GA | | 2-5 | 27-41-31 | TB0109Y | | A014 | BJ | TB0109A | A029 | 2 | | 001-099 |
| 0074 | 22 | | GA | | 0-7 | 27-41-31 | TB0109B | | A030 | 2 | TB0109A | C028 | 2 | | 001-099 |
| 0075 | 22 | | GA | | 0-7 | 27-41-31 | TB0109B | | A031 | 2 | TB0109A | C029 | 2 | | 001-099 |
| 0076 | 22 | | GA | | 0-7 | 31-31-62 | TB0109B | | C031 | 2 | TB0109Y | A032 | BJ | | 001-099 |
| 0077 | 22 | | GA | | 0-7 | 31-31-62 | TB0109B | | C030 | 2 | TB0109Y | A032 | BJ | | 001-099 |
| 0078 | 22 | | GA | | 3-1 | 31-31-62 | D41301J | | 47 | | TB0109B | A031 | 2 | | 001-099 |
| 0079 | 22 | | GA | | 3-1 | 31-31-62 | D41301J | | 49 | | TB0109B | A030 | 2 | | 001-099 |
| 0080 | 22 | | GA | | 3-1 | 31-31-62 | D41301J | | 48 | | TB0109Y | A032 | BJ | | 001-099 |
| 0081 | 22 | | GA | | 3-8 | 31-31-31 | D41301J | | 3 | | TB0109Y | A014 | BJ | | 115-199 |
| 0082 | 22 | | GA | | 3-5 | 27-41-31 | D41709J | | 9 | | TB0109A | C029 | 2 | | 001-099 |
| 0083 | 22 | | GA | | 2-6 | 27-61-12 | D00639B | | G08 | | GD01992 | DC.. | 2 | | 003-099 |
| 0084 | 22 | | GA | | 3-0 | 27-61-12 | D00637B | | C08 | | GD01992 | DC.. | 2 | | 003-099 |
| 0085 | 22 | | GA | | 3-6 | 27-61-12 | D00635B | | A07 | | GD01992 | DC.. | 2 | | 003-099 |
| 0086 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | F04 | | GD01983 | DC.. | 2 | | ALL |
| 0087 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | D04 | | GD01983 | DC.. | 2 | | ALL |
| 0088 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | C04 | | GD01983 | DC.. | 2 | | ALL |
| 0089 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | A04 | | GD01983 | DC.. | 2 | | ALL |
| 0090 | 22 | | GA | | 4-2 | 22-21-11 | D00349A | | H05 | | TB0109Y | A012 | BJ | | ALL |
| 0091 | 22 | | GA | | 3-8 | 22-21-11 | D41301J | | 22 | | TB0109Y | A012 | BJ | | ALL |
| 0092 | 22 | | GA | | 2-8 | 22-21-11 | D41775J | | 32 | | TB0109Y | A012 | BJ | | ALL |
| 0093 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | C05 | | GD01983 | DC.. | 2 | | ALL |
| 0094 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | D05 | | GD01983 | DC.. | 2 | | ALL |
| 0096 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | C01 | | D00701A | G01 | | | ALL |
| 0097 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | A01 | | D00701A | B08 | | | ALL |
| 0098 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | G05 | | D00701A | C05 | | | ALL |
| 0099 | 22 | | GA | | 3-9 | 22-21-11 | D00349A | | G04 | | D00701A | E03 | | | ALL |
| 0100 | 22 | | GA | | 2-8 | 22-21-11 | D00349A | | B05 | | D00703A | C05 | | | ALL |
| 0101 | 22 | | GA | | 2-8 | 22-21-11 | D00349A | | A05 | | D00703A | E03 | | | ALL |
| 0102 | 22 | | GA | | 2-8 | 22-21-11 | D00349A | | C02 | | D00703A | G01 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 55

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | | 286N1265 | | | | E3-1 SHELF (continued) | | | | | | | | | |
| 0103 | 22 | GA | | | 2-8 | 22-21-11 | D00349A | A02 | | | D00703A | B08 | | | ALL |
| 0104 | 22 | GA | | | 3-4 | 27-09-13 | GD01981 | DC.. | 2 | | D00637A | K13 | | | ALL |
| 0106 | 22 | GA | | | 2-7 | 27-21-22 | D41775J | 15 | | | D00709B | A01 | | | ALL |
| 0107 | 22 | GA | | | 2-7 | 27-21-22 | D41775J | 16 | | | D00709B | D01 | | | ALL |
| 0108 | 22 | GA | | | 2-7 | 27-21-22 | D41775J | 17 | | | D00709B | B01 | | | ALL |
| 0109 | 22 | GA | | | 2-9 | 27-21-22 | D41775J | 18 | | | D00709A | C06 | | | ALL |
| 0110 | 22 | GA | | | 3-4 | 27-41-11 | D00701A | G02 | | | D00705A | C04 | | | ALL |
| 0111 | 22 | GA | | | 3-4 | 27-41-11 | D00701A | A07 | | | D00705A | C05 | | | ALL |
| 0112 | 22 | GA | | | 3-4 | 27-41-11 | D00701A | B05 | | | D00705A | B04 | | | ALL |
| 0113 | 22 | GA | | | 3-4 | 27-41-11 | D00701A | E02 | | | D00705A | A04 | | | ALL |
| 0114 | 22 | GA | | | 3-1 | 27-41-11 | D00703A | G02 | | | D00705A | E04 | | | ALL |
| 0115 | 22 | GA | | | 3-1 | 27-41-11 | D00703A | A07 | | | D00705A | E05 | | | ALL |
| 0116 | 22 | GA | | | 3-1 | 27-41-11 | D00703A | B05 | | | D00705A | B05 | | | ALL |
| 0117 | 22 | GA | | | 3-1 | 27-41-11 | D00703A | E02 | | | D00705A | A05 | | | ALL |
| 0118Y | 22 | QB | | | 3-8 | 27-41-11 | D00705A | F07 | | | TB0109Z | 10 | BJ | | ALL |
| 0119Y | 22 | QB | | | 3-8 | 27-41-11 | D00705A | F08 | | | TB0109Z | 10 | BJ | | ALL |
| 0120Y | 22 | QB | | | 2-7 | 27-41-11 | D40676J | 12 | | | TB0109Z | 10 | BJ | | ALL |
| 0121Y | 22 | QB | | | 3-11 | 27-41-11 | D41709J | 2 | | | TB0109Z | 10 | BJ | | ALL |
| 0122Y | 22 | QB | | | 3-8 | 27-41-11 | D00705A | D04 | | | TB0109Y | C014 | BJ | | ALL |
| 0123Y | 22 | QB | | | 3-8 | 27-41-11 | D00705A | D05 | | | TB0109Y | A015 | BJ | | ALL |
| 0124Y | 22 | QB | | | 3-11 | 27-41-11 | D41709J | 3 | | | TB0109Y | C014 | BJ | | ALL |
| 0125Y | 22 | QB | | | 3-11 | 27-41-11 | D41709J | 4 | | | TB0109Y | A015 | BJ | | ALL |
| 0126Y | 22 | QB | | | 2-8 | 27-41-11 | D41775J | 9 | | | TB0109Y | C014 | BJ | | ALL |
| 0127Y | 22 | QB | | | 2-8 | 27-41-11 | D41775J | 10 | | | TB0109Y | A015 | BJ | | ALL |
| 0128 | 22 | GA | | | 3-5 | 27-41-11 | D41775J | 11 | | | D00705A | F12 | | | ALL |
| 0129 | 22 | GA | | | 3-5 | 27-41-11 | D41775J | 2 | | | D00705A | E12 | | | ALL |
| 0130 | 22 | GA | | | 0-7 | 27-61-13 | D00635A | A04 | | | D00635A | B05 | | | ALL |
| 0131 | 22 | GA | | | 0-7 | 27-61-13 | D00635A | C03 | | | D00635A | D02 | | | ALL |
| 0132 | 22 | GA | | | 0-7 | 27-61-13 | D00635A | A08 | | | D00635A | C08 | | | ALL |
| 0133 | 22 | GA | | | 0-7 | 27-61-13 | D00635A | B03 | | | D00635A | B02 | | | ALL |
| 0135 | 22 | GA | | | 0-7 | 27-61-13 | D00635A | C06 | | | D00635A | C05 | | | ALL |
| 0141 | 22 | GA | | | 0-7 | 27-61-17 | D00637B | C06 | | | D00637B | C07 | | | ALL |
| 0142 | 22 | GA | | | 0-7 | 27-61-17 | D00637B | A05 | | | D00637B | B06 | | | ALL |
| 0144 | 22 | GA | | | 0-7 | 27-61-17 | D00637B | E04 | | | D00637B | D03 | | | ALL |
| 0145 | 22 | GA | | | 0-7 | 27-61-17 | D00637B | B04 | | | D00637B | B03 | | | ALL |
| 0146 | 22 | GA | | | 0-7 | 27-61-18 | D00639B | A13 | | | D00639B | B14 | | | ALL |
| 0147 | 22 | GA | | | 0-7 | 27-61-18 | D00639B | E15 | | | D00639B | D14 | | | ALL |
| 0151 | 22 | GA | | | 0-7 | 27-61-18 | D00639B | C15 | | | D00639B | C13 | | | ALL |
| 0152 | 22 | GA | | | 0-7 | 27-61-18 | D00639B | E12 | | | D00639B | D11 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 56

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 0153 | 22 | | GA | | 0-7 | 27-61-18 | D00639B | | B12 | | D00639B | | B11 | | ALL |
| 0154Y | 20 | | QB | | 2-10 | 27-41-11 | D42026J | | 1 | | D41841J | | 5 | | ALL |
| 0155Y | 20 | | QB | | 2-10 | 27-41-11 | D42026J | | 2 | | D41841J | | 6 | | ALL |
| 0156Y | 22 | | QB | | 2-3 | 27-41-11 | D00787 | | A3 | | D41841J | | 7 | | ALL |
| 0157Y | 22 | | QB | | 2-3 | 27-41-11 | D00787 | | A1 | | D41841J | | 8 | | ALL |
| 0158Y | 22 | | QB | | 2-4 | 27-41-11 | D41709J | | 10 | | D41841J | | 9 | | ALL |
| 0159 | 22 | | GA | | 3-11 | 27-48-11 | D41709J | | 16 | | TB0109Y | A017 | BJ | | ALL |
| 0160 | 22 | | GA | | 2-4 | 27-48-11 | D41709J | | 17 | | D41841J | | 14 | | 001-009 |
| 0160 | 22 | | GA | | 2-4 | 27-48-11 | D41709J | | 17 | | TB0109Y | C016 | BJ | | 010-099 |
| 0160 | 22 | | GA | | 3-11 | 27-48-11 | D41709J | | 17 | | TB0109Y | C016 | BJ | | 115-199 |
| 0161 | 22 | | GA | | 2-4 | 27-48-11 | D41709J | | 18 | | D41841J | | 15 | | 001-009 |
| 0161 | 22 | | GA | | 2-4 | 27-48-11 | D41709J | | 18 | | TB0109Y | A016 | BJ | | 010-099 |
| 0161 | 22 | | GA | | 3-11 | 27-48-11 | D41709J | | 18 | | TB0109Y | A016 | BJ | | 115-199 |
| 0162 | 22 | | GA | | 2-7 | 27-48-11 | D40676J | | 6 | | TB0109Y | A017 | BJ | | ALL |
| 0163 | 22 | | GA | | 4-1 | 27-48-11 | D41841J | | 13 | | TB0109Y | A017 | BJ | | ALL |
| 0164 | 22 | | GA | | 4-1 | 27-48-11 | D41841J | | 14 | | TB0109Y | C016 | BJ | | 010-099, 115-199 |
| 0165Y | 22 | | QB | | 2-3 | 27-41-11 | D00705A | | F09 | | D41709J | | 8 | | ALL |
| 0166Y | 22 | | QB | | 2-3 | 27-41-11 | D00705A | | F10 | | D41709J | | 12 | | ALL |
| 0167 | 22 | | GA | | 4-1 | 27-48-11 | D41841J | | 15 | | TB0109Y | A016 | BJ | | 010-099, 115-199 |
| 0169Y | 22 | | QB | | 2-1 | 27-41-11 | D00787 | | A2 | | D41709J | | 7 | | ALL |
| 0170Y | 22 | | QB | | 3-5 | 27-41-11 | D00787 | | X1 | | TB0109Z | | 10 | BJ | ALL |
| 0171 | 22 | | GA | | 2-3 | 27-41-11 | D00787 | | X2 | | D41301J | | 42 | | ALL |
| 0173 | 22 | | GA | | 3-1 | 27-32-11 | D41709J | | 13 | | D41902J | | 2 | | ALL |
| 0174 | 22 | | GA | | 3-11 | 27-32-11 | D41709J | | 14 | | TB0109Y | C017 | BJ | | 001-099 |
| 0174 | 24 | | GK | | 3-11 | 27-32-11 | D41709J | | 14 | | TB0109Y | C017 | BJ | | 115-199 |
| 0175 | 24 | | GK | | 2-9 | 31-51-42 | D41709J | | 6 | | D41301J | | 4 | | ALL |
| 0176 | 22 | | GA | | 3-8 | 27-32-11 | TB0109Y | | C017 | BJ | D41301J | | 41 | | 001-099 |
| 0176 | 24 | | GK | | 3-8 | 27-32-11 | TB0109Y | | C017 | BJ | D41301J | | 41 | | 115-199 |
| 0177 | 22 | | GA | | 3-8 | 27-32-11 | D41301J | | 2 | | TB0109Y | C017 | BJ | | 001-099 |
| 0177 | 24 | | GK | | 3-8 | 27-32-11 | TB0109Y | | C017 | BJ | D41301J | | 2 | | 115-199 |
| 0180 | 24 | | GK | | 2-10 | 31-31-62 | D00349B | | H10 | | D41301J | | 37 | | 001-099 |
| 0180 | 24 | | GK | | 2-10 | 31-31-32 | D00349B | | H10 | | D41301J | | 37 | | 115-199 |
| 0181 | 24 | | GK | | 2-11 | 31-31-62 | D00635A | | H13 | | D41301J | | 38 | | 001-099 |
| 0181 | 24 | | GK | | 2-11 | 31-31-32 | D00635A | | H13 | | D41301J | | 38 | | 115-199 |
| 0182 | 24 | | GK | | 2-5 | 31-31-62 | D00637A | | H13 | | D41301J | | 39 | | 001-099 |
| 0182 | 24 | | GK | | 2-5 | 31-31-32 | D00637A | | H13 | | D41301J | | 39 | | 115-199 |
| 0183 | 24 | | GK | | 3-4 | 31-31-62 | D00639A | | H13 | | D41301J | | 40 | | 001-099 |
| 0183 | 24 | | GK | | 3-4 | 31-31-32 | D00639A | | H13 | | D41301J | | 40 | | 115-199 |
| 0201 | 22 | | GA | | 2-9 | 27-61-17 | D00701A | | C15 | | D00637B | | G14 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 57

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 0202 | 22 | | GA | | 2-9 | 27-61-17 | D00701A | | K13 | | D00637B | | G12 | | ALL |
| 0204 | 22 | | GA | | 3-5 | 27-61-17 | D00703A | | C15 | | D00637B | | F14 | | ALL |
| 0205 | 22 | | GA | | 3-5 | 27-61-17 | D00703A | | K13 | | D00637B | | F12 | | ALL |
| 0207 | 22 | | GA | | 2-1 | 27-61-17 | TB0109Z | | 57 | BJ | D00637A | | A15 | | ALL |
| 0208 | 22 | | GA | | 4-2 | 27-61-18 | D00701A | | F13 | | D00639A | | E11 | | ALL |
| 0209 | 22 | | GA | | 4-2 | 27-61-18 | D00701A | | J12 | | D00639A | | G03 | | ALL |
| 0210 | 22 | | GA | | 4-2 | 27-61-18 | D00701A | | B14 | | D00639A | | G05 | | ALL |
| 0213 | 22 | | GA | | 2-3 | 27-61-18 | D00703A | | B14 | | D00639A | | F05 | | ALL |
| 0214 | 22 | | GA | | 2-3 | 27-61-18 | D00703A | | J12 | | D00639A | | F03 | | ALL |
| 0215 | 22 | | GA | | 2-3 | 27-61-18 | D00703A | | F13 | | D00639A | | E12 | | ALL |
| 0216 | 22 | | GA | | 2-10 | 27-09-11 | D00701B | | A15 | | TB0109Z | | 57 | BJ | ALL |
| 0217 | 22 | | GA | | 3-6 | 27-09-11 | TB0109Z | | 57 | BJ | D00703B | | A15 | | ALL |
| 0218 | 22 | | GA | | 3-7 | 27-09-11 | D41902J | | 9 | | TB0109Z | | 57 | BJ | ALL |
| 0219 | 22 | | GA | | 1-11 | 27-09-12 | TB0109Z | | 47 | BJ | D00709B | | D07 | | ALL |
| 0220 | 22 | | GA | | 3-1 | 27-09-12 | TB0109Z | | 47 | BJ | D00349B | | H04 | | ALL |
| 0221 | 22 | | GA | | 2-9 | 27-09-12 | TB0109Z | | 47 | BJ | D00705A | | E14 | | ALL |
| 0223 | 22 | | GA | | 2-2 | 27-09-12 | TB0109Z | | 47 | BJ | D00637B | | D10 | | ALL |
| 0224 | 22 | | GA | | 2-1 | 27-09-12 | TB0109Z | | 47 | BJ | D00635B | | D02 | | ALL |
| 0225 | 22 | | GA | | 2-7 | 27-09-12 | TB0109Z | | 47 | BJ | D41779J | | 7 | | ALL |
| 0226 | 22 | | GA | | 2-8 | 27-09-13 | GD01982 | | DC.. | 2 | D00709B | | A03 | | ALL |
| 0227 | 22 | | GA | | 1-11 | 27-09-13 | TB0109Y | | C045 | BJ | D00709B | | B03 | | ALL |
| 0228 | 22 | | GA | | 3-1 | 27-09-13 | TB0109Y | | A045 | BJ | D00349B | | A12 | | ALL |
| 0229 | 22 | | GA | | 3-1 | 27-09-13 | TB0109Y | | C045 | BJ | D00349B | | B12 | | ALL |
| 0230 | 22 | | GA | | 2-3 | 27-09-13 | TB0109Y | | A045 | BJ | D00637A | | A12 | | ALL |
| 0231 | 22 | | GA | | 2-3 | 27-09-13 | TB0109Y | | C045 | BJ | D00637A | | A13 | | ALL |
| 0232 | 22 | | GA | | 2-7 | 27-09-13 | TB0109Y | | A045 | BJ | D41779J | | 8 | | ALL |
| 0233 | 22 | | GA | | 2-7 | 27-09-13 | TB0109Y | | C045 | BJ | D41779J | | 9 | | ALL |
| 0234 | 22 | | GA | | 2-7 | 27-09-13 | GD01982 | | DC.. | 2 | D00635A | | A12 | | ALL |
| 0235 | 22 | | GA | | 4-5 | 27-09-13 | GD01982 | | DC.. | 2 | D00639A | | A12 | | ALL |
| 0236 | 22 | | GA | | 2-10 | 27-09-14 | TB0109Y | | A061 | BJ | D00701B | | A13 | | ALL |
| 0237 | 22 | | GA | | 2-5 | 27-09-14 | D41779J | | 20 | | D00709B | | D14 | | 001-099 |
| 0237 | 22 | | GA | | 2-5 | 27-09-14 | D41779J | | 47 | | D00709B | | D14 | | 115-199 |
| 0238 | 22 | | GA | | 2-8 | 27-09-14 | D41779J | | 19 | | D00349B | | F04 | | 001-099 |
| 0238 | 22 | | GA | | 2-8 | 27-09-14 | D41779J | | 46 | | D00349B | | F04 | | 115-199 |
| 0239 | 22 | | GA | | 3-7 | 27-09-14 | TB0109Y | | A046 | BJ | D00639A | | C13 | | ALL |
| 0240 | 22 | | GA | | 2-3 | 27-09-14 | TB0109Y | | A046 | BJ | D00637A | | C13 | | ALL |
| 0241 | 22 | | GA | | 2-3 | 27-09-14 | TB0109Y | | A046 | BJ | D00635A | | C13 | | ALL |
| 0242 | 22 | | GA | | 3-6 | 27-09-14 | TB0109Y | | A061 | BJ | D00703B | | A13 | | ALL |
| 0243 | 22 | | GA | | 2-4 | 27-09-14 | TB0109Y | | A061 | BJ | D41779J | | 17 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 58

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|------------------------|----------|---------|---------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1265 | 286N1265 | | | | E3-1 SHELF (continued) | | | | | | | | | | | | |
| 0243 | 22 | | GA | | 2-4 | 27-09-14 | | TB0109Y | A061 | BJ | | D41779J | 44 | | | 115-199 | |
| 0244 | 22 | | GA | | 2-7 | 27-09-14 | | D41779J | 21 | | | TB0109Y | A046 | BJ | | 001-099 | |
| 0244 | 22 | | GA | | 2-7 | 27-09-14 | | D41779J | 48 | | | TB0109Y | A046 | BJ | | 115-199 | |
| 0249 | 22 | | GA | | 4-2 | 27-61-13 | | D00701B | G01 | | | D00703B | E01 | | | ALL | |
| 0250 | 22 | | GA | | 3-9 | 27-61-13 | | TB0109Z | 50 | BJ | | D00703B | C01 | | | ALL | |
| 0251 | 22 | | GA | | 3-11 | 27-61-13 | | D00703A | K12 | | | D00635B | F04 | | | ALL | |
| 0252 | 22 | | GA | | 3-11 | 27-61-13 | | D00703A | C14 | | | D00635B | F06 | | | ALL | |
| 0255 | 22 | | GA | | 2-3 | 27-61-13 | | D00701A | C14 | | | D00635B | G06 | | | ALL | |
| 0256 | 22 | | GA | | 2-3 | 27-61-13 | | D00701A | K12 | | | D00635B | G04 | | | ALL | |
| 0257 | 22 | | GA | | 2-7 | 27-61-13 | | TB0109Z | 57 | BJ | | D00635A | A15 | | | ALL | |
| 0258 | 22 | | GA | | 2-6 | 27-21-12 | | D00701A | A15 | | | D00709B | A12 | | | ALL | |
| 0259 | 22 | | GA | | 2-6 | 27-21-12 | | D00701A | H13 | | | D00709B | D12 | | | ALL | |
| 0260 | 22 | | GA | | 3-9 | 27-21-12 | | D00703A | A15 | | | D00709B | A13 | | | ALL | |
| 0261 | 22 | | GA | | 3-9 | 27-21-12 | | D00703A | H13 | | | D00709B | D13 | | | ALL | |
| 0262 | 22 | | GA | | 2-7 | 27-21-12 | | D00705A | K15 | | | D00709B | D08 | | | ALL | |
| 0263 | 22 | | GA | | 4-5 | 27-21-12 | | D00701A | C10 | | | D00703A | A10 | | | ALL | |
| 0264 | 22 | | GA | | 3-7 | 27-21-12 | | TB0109Z | 56 | BJ | | D00703A | C12 | | | ALL | |
| 0265 | 22 | | GA | | 2-3 | 27-21-12 | | TB0109Y | A054 | BJ | | D00709B | D04 | | | ALL | |
| 0266 | 22 | | GA | | 2-5 | 27-21-12 | | D00709B | C08 | | | D41779J | 11 | | | ALL | |
| 0267 | 22 | | GA | | 2-7 | 27-21-12 | | D00709A | D15 | | | D41779J | 12 | | | ALL | |
| 0268 | 22 | | GA | | 2-7 | 27-21-12 | | D00709A | A15 | | | D41779J | 13 | | | ALL | |
| 0269 | 22 | | GA | | 2-7 | 27-21-12 | | D00709A | B15 | | | D41779J | 14 | | | ALL | |
| 0270 | 22 | | GA | | 2-4 | 27-31-12 | | D00705A | A07 | | | D41779J | 35 | | | ALL | |
| 0271 | 22 | | GA | | 2-4 | 27-31-12 | | D00705A | A08 | | | D41779J | 36 | | | ALL | |
| 0299 | 22 | | GA | | 2-4 | 22-21-11 | | D00349A | F15 | | | D41795J | 21 | | | ALL | |
| 0304 | 22 | | GA | | 3-8 | 22-21-11 | | D00349B | A01 | | | D00701A | B15 | | | ALL | |
| 0305 | 22 | | GA | | 3-8 | 22-21-11 | | D00349B | C01 | | | D00701A | J13 | | | ALL | |
| 0308 | 22 | | GA | | 2-6 | 22-21-11 | | D00349B | C02 | | | D00703A | J13 | | | ALL | |
| 0309 | 22 | | GA | | 2-6 | 22-21-11 | | D00349B | A02 | | | D00703A | B15 | | | ALL | |
| 0310 | 22 | | GA | | 2-2 | 22-21-11 | | D00349A | H15 | | | D41789J | 3 | | | ALL | |
| 0311 | 22 | | GA | | 2-1 | 27-09-11 | | D41902J | 10 | | | D00703B | E15 | | | ALL | |
| 0312 | 22 | | GA | | 3-9 | 27-61-12 | | TB0109Y | A042 | BJ | | D00639A | B13 | | | ALL | |
| 0313 | 22 | | GA | | 2-5 | 27-61-12 | | TB0109Y | A042 | BJ | | D00637A | B13 | | | ALL | |
| 0314 | 22 | | GA | | 2-2 | 27-61-12 | | TB0109Y | A042 | BJ | | D00635A | B13 | | | ALL | |
| 0315 | 22 | | GA | | 2-9 | 27-61-12 | | TB0109Y | A042 | BJ | | D41779J | 22 | | | ALL | |
| 0316 | 22 | | GA | | 3-4 | 27-61-18 | | TB0109Z | 57 | BJ | | D00639A | A15 | | | ALL | |
| 0317 | 22 | | GA | | 2-3 | 27-09-14 | | D41779J | 18 | | | D00705B | F04 | | | 001-099 | |
| 0317 | 22 | | GA | | 2-3 | 27-09-14 | | D41779J | 45 | | | D00705B | F04 | | | 115-199 | |
| 0318 | 22 | | GA | | 2-4 | 27-21-12 | | TB0109Y | A054 | BJ | | D41779J | 10 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 59

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | | 286N1265 | | | | E3-1 SHELF (continued) | | | | | | | | | |
| 0319 | 22 | GA | | | 3-1 | 27-21-12 | TB0109Y | A054 | BJ | | D41795J | 8 | | | ALL |
| 0322 | 22 | GA | | | 2-8 | 22-21-11 | D00349B | H05 | | | D41779J | 24 | | | ALL |
| 0323 | 22 | GA | | | 2-10 | 22-21-11 | D00349B | A04 | | | TB0109Z | 57 | BJ | | ALL |
| 0325 | 22 | GA | | | 2-8 | 22-21-11 | D00349B | K08 | | | D41779J | 31 | | | ALL |
| 0326 | 22 | GA | | | 2-8 | 22-21-11 | D00349B | K07 | | | D41779J | 32 | | | ALL |
| 0327 | 22 | GA | | | 2-3 | 22-22-11 | D41779J | 33 | | | D00705B | E05 | | | ALL |
| 0328 | 22 | GA | | | 2-4 | 22-24-11 | D41779J | 23 | | | D00705A | C11 | | | ALL |
| 0329 | 22 | GA | | | 2-4 | 22-24-11 | D41779J | 34 | | | D00705A | A09 | | | ALL |
| 0330 | 22 | GA | | | 2-4 | 22-24-11 | D41779J | 1 | | | D00705A | C14 | | | ALL |
| 0331 | 22 | GA | | | 3-4 | 27-41-11 | D00701A | H12 | | | D00705A | G13 | | | ALL |
| 0332 | 22 | GA | | | 3-4 | 27-41-11 | D00701A | A14 | | | D00705A | G14 | | | ALL |
| 0333 | 22 | GA | | | 3-1 | 27-41-11 | D00703A | H12 | | | D00705A | J13 | | | ALL |
| 0334 | 22 | GA | | | 3-1 | 27-41-11 | D00703A | A14 | | | D00705A | J14 | | | ALL |
| 0335Y | 22 | QB | | | 2-4 | 27-41-11 | D00705A | A13 | | | D41779J | 2 | | | ALL |
| 0338Y | 22 | QB | | | 2-4 | 27-41-11 | D00705A | A14 | | | D41779J | 3 | | | ALL |
| 0341 | 22 | GA | | | 2-4 | 27-41-11 | D41779J | 4 | | | D00705A | C12 | | | ALL |
| 0345 | 22 | GA | | | 0-7 | 27-61-13 | D00635B | C07 | | | D00635B | C06 | | | ALL |
| 0346 | 22 | GA | | | 0-7 | 27-61-13 | D00635B | A05 | | | D00635B | B06 | | | ALL |
| 0347 | 22 | GA | | | 0-7 | 27-61-13 | D00635B | C04 | | | D00635B | D03 | | | ALL |
| 0349 | 22 | GA | | | 0-7 | 27-61-13 | D00635B | B03 | | | D00635B | B04 | | | ALL |
| 0350 | 22 | GA | | | 0-7 | 27-61-17 | D00637B | A13 | | | D00637B | B14 | | | ALL |
| 0355 | 22 | GA | | | 0-7 | 27-61-17 | D00637B | C14 | | | D00637B | C15 | | | ALL |
| 0356 | 22 | GA | | | 0-7 | 27-61-17 | D00637B | E12 | | | D00637B | D11 | | | ALL |
| 0357 | 22 | GA | | | 0-7 | 27-61-17 | D00637B | B12 | | | D00637B | B11 | | | ALL |
| 0358 | 22 | GA | | | 0-7 | 27-61-18 | D00639A | A04 | | | D00639A | B05 | | | ALL |
| 0359 | 22 | GA | | | 0-7 | 27-61-18 | D00639A | E06 | | | D00639A | D05 | | | ALL |
| 0363 | 22 | GA | | | 0-7 | 27-61-18 | D00639A | C06 | | | D00639A | C04 | | | ALL |
| 0364 | 22 | GA | | | 0-7 | 27-61-18 | D00639A | E03 | | | D00639A | D02 | | | ALL |
| 0365 | 22 | GA | | | 0-7 | 27-61-18 | D00639A | B03 | | | D00639A | B02 | | | ALL |
| 0366Y | 22 | QB | | | 2-7 | 27-41-11 | D00705A | C07 | | | D41795J | 22 | | | ALL |
| 0367Y | 22 | QB | | | 2-7 | 27-41-11 | D00705A | C08 | | | D41795J | 23 | | | ALL |
| 0368Y | 22 | QB | | | 2-6 | 27-41-11 | D00705A | C09 | | | TB0109Y | C091 | BJ | | ALL |
| 0369Y | 22 | QB | | | 2-4 | 27-41-11 | D41795J | 24 | | | TB0109Y | C091 | BJ | | ALL |
| 0370Y | 22 | QB | | | 2-10 | 27-41-11 | D41779J | 6 | | | TB0109Y | C091 | BJ | | ALL |
| 0371 | 22 | GA | | | 0-7 | 27-61-18 | D00639A | B08 | | | D00639A | C08 | | | ALL |
| 0380 | 22 | GA | | | 2-4 | 27-41-11 | D00705A | B13 | | | D41779J | 25 | | | 001-099 |
| 0380 | 22 | GA | | | 2-4 | 27-41-11 | D00705A | B13 | | | D41779J | 42 | | | 115-199 |
| 0381 | 22 | GA | | | 2-4 | 27-41-11 | D00705A | B14 | | | D41779J | 26 | | | 001-099 |
| 0381 | 22 | GA | | | 2-4 | 27-41-11 | D00705A | B14 | | | D41779J | 43 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 60

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 0400 | 22 | | GA | | 2-4 | 27-09-11 | D00701C | | 5 | | GD01985 | AC.. | 2 | | ALL |
| 0401 | 16 | | GA | | 2-4 | 27-09-11 | D00701C | | 10 | | GD01985 | DC.. | 2 | | ALL |
| 0402 | 16 | | GA | | 2-4 | 27-09-11 | D00701C | | 9 | | GD01985 | DC.. | 2 | | ALL |
| 0403 | 16 | | GA | | 2-4 | 27-09-11 | D00701C | | 2 | | GD01985 | DC.. | 2 | | ALL |
| 0404 | 16 | | GA | | 2-4 | 27-09-11 | D00701C | | 7 | | GD01985 | DC.. | 2 | | ALL |
| 0405 | 16 | | GA | | 2-4 | 27-09-11 | D00701C | | 3 | | GD01985 | DC.. | 2 | | ALL |
| 0406 | 16 | | GA | | 2-4 | 27-09-11 | D00701C | | 11 | | GD01985 | AC.. | 2 | | ALL |
| 0407 | 16 | | GA | | 2-4 | 27-09-11 | D00701C | | 8 | | GD01985 | ST.. | 2 | | ALL |
| 0408 | 16 | | GA | | 4-8 | 27-09-11 | D00703C | | 10 | | GD01981 | DC.. | 2 | | ALL |
| 0409 | 16 | | GA | | 4-8 | 27-09-11 | D00703C | | 9 | | GD01981 | DC.. | 2 | | ALL |
| 0410 | 16 | | GA | | 4-8 | 27-09-11 | D00703C | | 2 | | GD01981 | DC.. | 2 | | ALL |
| 0411 | 16 | | GA | | 4-8 | 27-09-11 | D00703C | | 7 | | GD01981 | DC.. | 2 | | ALL |
| 0412 | 16 | | GA | | 4-8 | 27-09-11 | D00703C | | 3 | | GD01981 | DC.. | 2 | | ALL |
| 0413 | 16 | | GA | | 4-8 | 27-09-11 | D00703C | | 11 | | GD01981 | AC.. | 2 | | ALL |
| 0414 | 16 | | GA | | 4-8 | 27-09-11 | D00703C | | 8 | | GD01981 | ST.. | 2 | | ALL |
| 0415 | 22 | | GA | | 1-11 | 27-09-12 | TB0109Y | A092 | BJ | | D00349B | C14 | | | ALL |
| 0416 | 22 | | GA | | 2-4 | 27-09-12 | TB0109Y | A092 | BJ | | D00705B | K12 | | | ALL |
| 0417 | 22 | | GA | | 2-4 | 27-09-12 | TB0109Y | C092 | BJ | | D00639B | D02 | | | ALL |
| 0418 | 22 | | GA | | 2-11 | 27-09-12 | TB0109Y | A093 | BJ | | D00637A | D01 | | | ALL |
| 0419 | 22 | | GA | | 3-9 | 27-09-12 | TB0109Z | 85 | BJ | | D41399J | 18 | | | ALL |
| 0420 | 22 | | GA | | 3-6 | 27-09-12 | TB0109Z | 85 | BJ | | D41783J | 12 | | | ALL |
| 0421 | 22 | | GA | | 2-11 | 27-09-12 | TB0109Z | 85 | BJ | | D00635B | D10 | | | ALL |
| 0422 | 22 | | GA | | 3-0 | 27-09-13 | TB0109Y | A084 | BJ | | D00635A | K13 | | | ALL |
| 0423 | 22 | | GA | | 3-0 | 27-09-13 | TB0109Y | C084 | BJ | | D00635A | J13 | | | ALL |
| 0424 | 22 | | GA | | 1-11 | 27-09-13 | TB0109Y | A084 | BJ | | D00705B | H06 | | | ALL |
| 0425 | 22 | | GA | | 1-11 | 27-09-13 | TB0109Y | C084 | BJ | | D00705B | H05 | | | ALL |
| 0426 | 22 | | GA | | 3-9 | 27-09-13 | TB0109Y | A084 | BJ | | D41399J | 16 | | | ALL |
| 0427 | 22 | | GA | | 3-9 | 27-09-13 | TB0109Y | C084 | BJ | | D41399J | 17 | | | ALL |
| 0428 | 22 | | GA | | 3-6 | 27-09-13 | TB0109Y | A084 | BJ | | D41783J | 5 | | | ALL |
| 0429 | 22 | | GA | | 3-6 | 27-09-13 | TB0109Y | C084 | BJ | | D41783J | 6 | | | ALL |
| 0431 | 22 | | GA | | 2-8 | 27-21-12 | D00709B | D15 | | | GD01982 | DC.. | 2 | | ALL |
| 0432 | 22 | | GA | | 2-8 | 27-21-12 | D00709B | C15 | | | GD01982 | DC.. | 2 | | ALL |
| 0433 | 22 | | GA | | 2-8 | 27-21-12 | D00709B | B15 | | | GD01982 | DC.. | 2 | | ALL |
| 0434 | 16 | | GA | | 2-7 | 27-21-12 | D00709C | | 3 | | GD01982 | DC.. | 2 | | ALL |
| 0435 | 16 | | GA | | 2-7 | 27-21-12 | D00709C | | 4 | | GD01982 | DC.. | 2 | | ALL |
| 0436 | 16 | | GA | | 2-7 | 27-21-12 | D00709C | | 2 | | GD01982 | DC.. | 2 | | ALL |
| 0438 | 22 | | GA | | 2-1 | 27-61-13 | D00701B | H03 | | | D00635B | G14 | | | ALL |
| 0439 | 22 | | GA | | 2-1 | 27-61-13 | D00701B | F03 | | | D00635B | G12 | | | ALL |
| 0441 | 22 | | GA | | 3-10 | 27-61-13 | D00703B | H03 | | | D00635B | F14 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 61

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | | 286N1265 | | | | E3-1 SHELF (continued) | | | | | | | | | |
| 0442 | 22 | GA | | | 3-10 | 27-61-13 | D00703B | F03 | | | D00635B | F12 | | | ALL |
| 0444 | 16 | GA | | | 2-7 | 27-61-13 | GD01981 | DC.. | 2 | | D00635C | 8 | | | ALL |
| 0445 | 16 | GA | | | 2-7 | 27-61-13 | GD01981 | DC.. | 2 | | D00635C | 3 | | | ALL |
| 0446 | 16 | GA | | | 2-7 | 27-61-13 | GD01981 | DC.. | 2 | | D00635C | 2 | | | ALL |
| 0447 | 16 | GA | | | 2-7 | 27-61-13 | GD01981 | DC.. | 2 | | D00635C | 7 | | | ALL |
| 0448 | 20 | GA | | | 2-7 | 27-61-13 | GD01980 | DC.. | 2 | | D00635C | 6 | | | ALL |
| 0449 | 20 | GA | | | 2-7 | 27-61-13 | GD01980 | DC.. | 2 | | D00635C | 5 | | | ALL |
| 0451 | 22 | GA | | | 2-9 | 27-61-17 | D00701B | F04 | | | D00637A | G03 | | | ALL |
| 0452 | 22 | GA | | | 2-9 | 27-61-17 | D00701B | H04 | | | D00637A | G05 | | | ALL |
| 0454 | 22 | GA | | | 2-9 | 27-61-17 | D00701B | K01 | | | D00637A | E11 | | | ALL |
| 0455 | 22 | GA | | | 3-5 | 27-61-17 | D00703B | K01 | | | D00637A | E12 | | | ALL |
| 0457 | 22 | GA | | | 3-5 | 27-61-17 | D00703B | H04 | | | D00637A | F05 | | | ALL |
| 0458 | 22 | GA | | | 3-5 | 27-61-17 | D00703B | F04 | | | D00637A | F03 | | | ALL |
| 0459 | 16 | GA | | | 3-1 | 27-61-17 | GD01980 | DC.. | 2 | | D00637C | 8 | | | ALL |
| 0460 | 16 | GA | | | 3-1 | 27-61-17 | GD01980 | DC.. | 2 | | D00637C | 3 | | | ALL |
| 0461 | 16 | GA | | | 3-1 | 27-61-17 | GD01980 | DC.. | 2 | | D00637C | 2 | | | ALL |
| 0462 | 16 | GA | | | 3-1 | 27-61-17 | GD01980 | DC.. | 2 | | D00637C | 7 | | | ALL |
| 0467 | 22 | GA | | | 3-11 | 27-61-18 | D00701B | H05 | | | D00639B | G06 | | | ALL |
| 0468 | 22 | GA | | | 3-11 | 27-61-18 | D00701B | F05 | | | D00639B | G04 | | | ALL |
| 0469 | 22 | GA | | | 2-0 | 27-61-18 | D00703B | F05 | | | D00639B | F04 | | | ALL |
| 0470 | 22 | GA | | | 2-0 | 27-61-18 | D00703B | H05 | | | D00639B | F06 | | | ALL |
| 0472 | 16 | GA | | | 4-5 | 27-61-18 | GD01980 | DC.. | 2 | | D00639C | 8 | | | ALL |
| 0473 | 16 | GA | | | 4-5 | 27-61-18 | GD01980 | DC.. | 2 | | D00639C | 3 | | | ALL |
| 0474 | 16 | GA | | | 4-5 | 27-61-18 | GD01980 | DC.. | 2 | | D00639C | 2 | | | ALL |
| 0475 | 16 | GA | | | 4-5 | 27-61-18 | GD01980 | DC.. | 2 | | D00639C | 7 | | | ALL |
| 0480 | 22 | GA | | | 4-2 | 27-61-18 | D00701B | C07 | | | D00703B | A07 | | | ALL |
| 0481 | 22 | GA | | | 2-3 | 27-61-18 | TB0109Z | 114 | BJ | | D00703B | C05 | | | ALL |
| 0482 | 22 | GA | | | 4-2 | 22-21-11 | D41399J | 11 | | | TB0109Y | A088 | BJ | | ALL |
| 0483 | 22 | GA | | | 1-11 | 22-21-11 | D00349B | C15 | | | TB0109Y | A088 | BJ | | ALL |
| 0484 | 22 | GA | | | 3-11 | 22-21-11 | D41783J | 11 | | | TB0109Y | A088 | BJ | | ALL |
| 0485 | 22 | GA | | | 3-7 | 22-22-11 | D41399J | 1 | | | D00705B | J14 | | | ALL |
| 0486 | 22 | GA | | | 4-2 | 22-22-11 | D41399J | 2 | | | TB0109Y | C088 | BJ | | ALL |
| 0487 | 22 | GA | | | 2-4 | 22-22-11 | D00705B | J15 | | | TB0109Y | C088 | BJ | | ALL |
| 0488 | 22 | GA | | | 3-11 | 22-22-11 | D41783J | 3 | | | TB0109Y | C088 | BJ | | ALL |
| 0489 | 22 | GA | | | 2-9 | 22-22-11 | D41783J | 2 | | | D41399J | 6 | | | ALL |
| 0490 | 22 | GA | | | 3-5 | 22-22-11 | D41783J | 4 | | | D00705A | J12 | | | ALL |
| 0491 | 22 | GA | | | 3-11 | 22-24-11 | D41783J | 1 | | | TB0109Y | A090 | BJ | | ALL |
| 0492 | 22 | GA | | | 4-2 | 22-24-11 | D41399J | 25 | | | TB0109Y | A090 | BJ | | ALL |
| 0493 | 22 | GA | | | 2-4 | 22-24-11 | D00705B | H15 | | | TB0109Y | A090 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 62

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 0494 | 22 | | GA | | 2-7 | 27-41-11 | D00705C | | 3 | | GD01986 | DC.. | 2 | | ALL |
| 0495 | 22 | | GA | | 2-7 | 27-41-11 | D00705C | | 2 | | GD01986 | DC.. | 2 | | ALL |
| 0496 | 22 | | GA | | 2-7 | 27-41-11 | D00705C | | 8 | | GD01986 | DC.. | 2 | | ALL |
| 0497 | 22 | | GA | | 2-7 | 27-41-11 | D00705C | | 7 | | GD01986 | DC.. | 2 | | ALL |
| 0498 | 22 | | GA | | 2-7 | 27-41-11 | D00705C | | 11 | | GD01986 | DC.. | 2 | | ALL |
| 0499 | 22 | | GA | | 2-7 | 27-41-11 | D00705C | | 10 | | GD01986 | ST.. | 2 | | ALL |
| 0500 | 22 | | GA | | 2-9 | 27-41-11 | D00705B | H11 | | | GD01986 | DC.. | 2 | | ALL |
| 0501 | 22 | | GA | | 2-9 | 27-41-11 | D00705B | H08 | | | GD01986 | DC.. | 2 | | ALL |
| 0502 | 22 | | GA | | 2-9 | 27-41-11 | D00705B | H09 | | | GD01986 | DC.. | 2 | | ALL |
| 0503 | 22 | | GA | | 2-9 | 27-41-11 | D00705B | H12 | | | GD01986 | DC.. | 2 | | ALL |
| 0504 | 22 | | GA | | 0-7 | 27-61-13 | D00635B | A13 | | | D00635B | B14 | | | ALL |
| 0508 | 22 | | GA | | 0-7 | 27-61-13 | D00635B | B12 | | | D00635B | B11 | | | ALL |
| 0510 | 22 | | GA | | 0-7 | 27-61-13 | D00635B | C15 | | | D00635B | C14 | | | ALL |
| 0512 | 22 | | GA | | 0-7 | 27-61-13 | D00635B | C12 | | | D00635B | D11 | | | ALL |
| 0513 | 16 | | GA | | 1-11 | 27-61-13 | D00635C | | 10 | | GD01985 | DC.. | 2 | | ALL |
| 0514 | 16 | | GA | | 1-11 | 27-61-13 | D00635C | | 9 | | GD01985 | DC.. | 2 | | ALL |
| 0515 | 22 | | GA | | 0-7 | 27-61-17 | D00637A | A04 | | | D00637A | B05 | | | ALL |
| 0520 | 22 | | GA | | 2-7 | 27-61-13 | D41399J | | 29 | | D00635B | H12 | | | ALL |
| 0521 | 22 | | GA | | 2-3 | 27-61-13 | D41399J | | 30 | | GD01981 | DC.. | 2 | | ALL |
| 0522 | 22 | | GA | | 0-7 | 27-61-17 | D00637A | B08 | | | D00637A | C08 | | | ALL |
| 0523 | 22 | | GA | | 2-11 | 27-61-17 | TB0109Y | A091 | BJ | | D00637A | B07 | | | ALL |
| 0524 | 22 | | GA | | 2-11 | 27-61-17 | D00637A | A07 | | | TB0109Y | A091 | BJ | | ALL |
| 0560 | 22 | | GA | | 0-7 | 27-61-17 | D00637A | C05 | | | D00637A | C06 | | | ALL |
| 0561 | 22 | | GA | | 0-7 | 27-61-17 | D00637A | E03 | | | D00637A | D02 | | | ALL |
| 0562 | 22 | | GA | | 0-7 | 27-61-17 | D00637A | B03 | | | D00637A | B02 | | | ALL |
| 0563 | 16 | | GA | | 2-10 | 27-61-17 | D00637C | | 10 | | GD01982 | DC.. | 2 | | ALL |
| 0564 | 16 | | GA | | 2-10 | 27-61-17 | D00637C | | 9 | | GD01982 | DC.. | 2 | | ALL |
| 0565 | 20 | | GA | | 2-10 | 27-61-17 | D00637C | | 6 | | GD01982 | DC.. | 2 | | ALL |
| 0566 | 20 | | GA | | 2-10 | 27-61-17 | D00637C | | 5 | | GD01982 | DC.. | 2 | | ALL |
| 0570 | 22 | | GA | | 0-7 | 27-61-18 | D00639B | C07 | | | D00639B | C05 | | | ALL |
| 0571 | 22 | | GA | | 0-7 | 27-61-18 | D00639B | A05 | | | D00639B | B06 | | | ALL |
| 0572 | 22 | | GA | | 0-7 | 27-61-18 | D00639B | E07 | | | D00639B | D06 | | | ALL |
| 0573 | 22 | | GA | | 0-7 | 27-61-18 | D00639B | E04 | | | D00639B | D03 | | | ALL |
| 0574 | 22 | | GA | | 0-7 | 27-61-18 | D00639B | B04 | | | D00639B | B03 | | | ALL |
| 0575 | 16 | | GA | | 4-5 | 27-61-18 | D00639C | | 10 | | GD01980 | DC.. | 2 | | ALL |
| 0576 | 16 | | GA | | 4-5 | 27-61-18 | D00639C | | 9 | | GD01980 | DC.. | 2 | | ALL |
| 0577 | 20 | | GA | | 4-5 | 27-61-18 | D00639C | | 6 | | GD01980 | DC.. | 2 | | ALL |
| 0578 | 20 | | GA | | 4-5 | 27-61-18 | D00639C | | 5 | | GD01980 | DC.. | 2 | | ALL |
| 0580 | 20 | | GA | | 3-6 | 22-21-11 | D00349C | | 1 | | GD01983 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 63

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|----|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | | | | | | E3-1 SHELF (continued) | | | | | | | | | |
| 0581 | 20 | GA | | | 3-6 | 22-21-11 | D00349C | | 4 | | GD01983 | ST.. | 2 | | ALL |
| 0582 | 16 | GA | | | 3-6 | 22-21-11 | D00349C | | 2 | | GD01983 | DC.. | 2 | | ALL |
| 0583 | 16 | GA | | | 3-6 | 22-21-11 | D00349C | | 3 | | GD01983 | DC.. | 2 | | ALL |
| 0584 | 20 | GA | | | 3-6 | 22-21-11 | D00349C | | 6 | | GD01983 | ST.. | 2 | | ALL |
| 0585 | 16 | GA | | | 3-6 | 22-21-11 | D00349C | | 8 | | GD01983 | ST.. | 2 | | ALL |
| 0586 | 16 | GA | | | 3-6 | 22-21-11 | D00349C | | 9 | | GD01983 | DC.. | 2 | | ALL |
| 0587 | 16 | GA | | | 3-6 | 22-21-11 | D00349C | | 10 | | GD01983 | DC.. | 2 | | ALL |
| 0588 | 22 | GA | | | 2-5 | 27-09-12 | D00639A | D01 | | | TB0109Y | A093 | BJ | | ALL |
| 0589 | 22 | GA | | | 4-2 | 27-09-12 | D41399J | | 28 | | TB0109Y | A093 | BJ | | ALL |
| 0590 | 22 | GA | | | 2-10 | 27-09-12 | D00637B | D02 | | | TB0109Y | C092 | BJ | | ALL |
| 0591 | 22 | GA | | | 4-2 | 27-09-12 | D41399J | | 27 | | TB0109Y | C092 | BJ | | ALL |
| 0592 | 22 | GA | | | 3-11 | 27-09-12 | D41783J | | 10 | | TB0109Y | A092 | BJ | | ALL |
| 0593 | 22 | GA | | | 4-2 | 27-09-12 | D41399J | | 26 | | TB0109Y | A092 | BJ | | ALL |
| 0609 | 22 | GA | | | 2-3 | 27-09-14 | D41787J | | 18 | | TB0109Y | C095 | BJ | | ALL |
| 0610 | 22 | GA | | | 2-3 | 27-09-14 | D41787J | | 24 | | TB0109Y | A095 | BJ | | ALL |
| 0611 | 22 | GA | | | 2-8 | 27-09-14 | D41787J | | 23 | | TB0109Y | C112 | BJ | | ALL |
| 0612 | 22 | GA | | | 2-7 | 27-09-14 | D41437J | | 14 | | TB0109Z | 115 | BJ | | ALL |
| 0613 | 22 | GA | | | 2-5 | 27-09-11 | D41964J | | 2 | | D00701B | E15 | | | ALL |
| 0614 | 22 | GA | | | 4-9 | 27-09-11 | D41964J | | 4 | | TB0109Z | 116 | BJ | | ALL |
| 0615 | 22 | GA | | | 4-1 | 27-09-11 | D00701B | | K15 | | TB0109Z | 116 | BJ | | ALL |
| 0616 | 22 | GA | | | 2-3 | 27-09-11 | D00703B | | K15 | | TB0109Z | 116 | BJ | | ALL |
| 0617 | 22 | GA | | | 4-1 | 27-09-14 | TB0109Y | C117 | BJ | | D00701B | K13 | | | ALL |
| 0618 | 22 | GA | | | 2-7 | 27-09-14 | TB0109Y | C117 | BJ | | D41437J | 19 | | | ALL |
| 0619 | 22 | GA | | | 3-8 | 27-09-14 | TB0109Y | C112 | BJ | | D00709A | C15 | | | ALL |
| 0620 | 22 | GA | | | 2-8 | 27-09-14 | TB0109Z | | 115 | BJ | D41787J | 17 | | | ALL |
| 0621 | 22 | GA | | | 1-11 | 27-09-14 | TB0109Y | C095 | BJ | | D00349B | G10 | | | ALL |
| 0622 | 22 | GA | | | 2-4 | 27-09-14 | TB0109Y | A095 | BJ | | D00705B | A15 | | | ALL |
| 0623 | 22 | GA | | | 2-1 | 27-09-14 | TB0109Z | | 115 | BJ | D00639A | H14 | | | ALL |
| 0624 | 22 | GA | | | 3-4 | 27-09-14 | TB0109Z | | 115 | BJ | D00637A | H14 | | | ALL |
| 0625 | 22 | GA | | | 3-10 | 27-09-14 | TB0109Z | | 115 | BJ | D00635A | H14 | | | ALL |
| 0626 | 22 | GA | | | 2-3 | 27-09-14 | TB0109Y | C117 | BJ | | D00703B | K13 | | | ALL |
| 0627 | 22 | GA | | | 2-7 | 27-09-14 | D41437J | | 18 | | TB0109Y | C112 | BJ | | ALL |
| 0628 | 22 | GA | | | 2-7 | 27-21-12 | TB0109Y | A117 | BJ | | D41437J | 4 | | | ALL |
| 0629 | 22 | GA | | | 3-11 | 27-21-12 | D41838J | | 1 | | TB0109Y | A117 | BJ | | ALL |
| 0630 | 22 | GA | | | 3-0 | 27-21-12 | TB0109Y | A018 | BJ | | D00709A | D12 | | | ALL |
| 0631 | 22 | GA | | | 3-6 | 27-21-12 | TB0109Y | A117 | BJ | | D00709B | A14 | | | ALL |
| 0632 | 22 | GA | | | 2-8 | 27-21-12 | TB0109Y | A018 | BJ | | D41775J | 38 | | | ALL |
| 0633 | 22 | GA | | | 2-8 | 27-21-12 | TB0109Y | A117 | BJ | | D41787J | 6 | | | ALL |
| 0634 | 22 | GA | | | 2-11 | 27-31-12 | D00705A | A02 | | | TB0109Y | A111 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 64

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 0635 | 22 | | GA | | 2-11 | 27-31-12 | D00705A | A03 | | | TB0109Y | C111 | BJ | | ALL |
| 0636 | 22 | | GA | | 3-0 | 27-31-12 | D41841J | 3 | | | TB0109Y | A111 | BJ | | ALL |
| 0637 | 22 | | GA | | 3-0 | 27-31-12 | D41841J | 4 | | | TB0109Y | C111 | BJ | | ALL |
| 0638 | 22 | | GA | | 2-8 | 27-31-12 | D41787J | 7 | | | TB0109Y | A111 | BJ | | ALL |
| 0639 | 22 | | GA | | 2-8 | 27-31-12 | D41787J | 8 | | | TB0109Y | C111 | BJ | | ALL |
| 0640 | 22 | | GA | | 2-9 | 27-31-12 | TB0109Y | A112 | BJ | | D00705B | A11 | | | ALL |
| 0641 | 22 | | GA | | 2-8 | 27-31-12 | TB0109Y | A112 | BJ | | D41787J | 9 | | | ALL |
| 0642 | 22 | | GA | | 2-7 | 27-31-12 | TB0109Y | A112 | BJ | | D41437J | 5 | | | ALL |
| 0645 | 22 | | GA | | 3-10 | 27-61-13 | TB0109Z | 116 | BJ | | D00635A | K15 | | | ALL |
| 0646 | 22 | | GA | | 2-6 | 27-61-12 | D00635A | F13 | | | D00637A | E13 | | | ALL |
| 0647 | 22 | | GA | | 2-6 | 27-61-12 | D00635A | D13 | | | D00637A | G13 | | | ALL |
| 0648 | 22 | | GA | | 3-10 | 27-61-12 | D00635A | E13 | | | D00639A | F13 | | | ALL |
| 0649 | 22 | | GA | | 3-10 | 27-61-12 | D00635A | G13 | | | D00639A | D13 | | | ALL |
| 0650 | 22 | | GA | | 2-6 | 27-61-12 | D00635A | F14 | | | D00637A | E14 | | | ALL |
| 0651 | 22 | | GA | | 2-6 | 27-61-12 | D00635A | D14 | | | D00637A | G14 | | | ALL |
| 0652 | 22 | | GA | | 3-10 | 27-61-12 | D00635A | E14 | | | D00639A | F14 | | | ALL |
| 0653 | 22 | | GA | | 3-10 | 27-61-12 | D00635A | G14 | | | D00639A | D14 | | | ALL |
| 0654 | 22 | | GA | | 2-6 | 27-61-12 | D00635A | F15 | | | D00637A | D15 | | | ALL |
| 0655 | 22 | | GA | | 2-6 | 27-61-12 | D00635A | E15 | | | D00637A | G15 | | | ALL |
| 0656 | 22 | | GA | | 2-7 | 27-09-14 | D41437J | 15 | | | D41787J | 13 | | | ALL |
| 0657 | 22 | | GA | | 3-10 | 27-61-12 | D00635A | D15 | | | D00639A | F15 | | | ALL |
| 0658 | 22 | | GA | | 3-10 | 27-61-12 | D00635A | G15 | | | D00639A | E15 | | | ALL |
| 0659 | 22 | | GA | | 3-4 | 27-61-12 | D00637A | D13 | | | D00639A | G13 | | | ALL |
| 0660 | 22 | | GA | | 3-4 | 27-61-12 | D00637A | F13 | | | D00639A | E13 | | | ALL |
| 0661 | 22 | | GA | | 3-4 | 27-61-12 | D00637A | D14 | | | D00639A | G14 | | | ALL |
| 0662 | 22 | | GA | | 3-4 | 27-61-12 | D00637A | F14 | | | D00639A | E14 | | | ALL |
| 0663 | 22 | | GA | | 3-4 | 27-61-12 | D00637A | E15 | | | D00639A | G15 | | | ALL |
| 0664 | 22 | | GA | | 3-4 | 27-61-12 | D00637A | F15 | | | D00639A | D15 | | | ALL |
| 0668 | 22 | | GA | | 0-9 | 27-61-12 | D00639C | 4 | | | D00639A | B07 | | | ALL |
| 0669 | 22 | | GA | | 2-8 | 27-61-12 | D00637C | 4 | | | TB0109Y | A091 | BJ | | ALL |
| 0670 | 22 | | GA | | 0-9 | 27-61-12 | D00635C | 4 | | | D00635A | B07 | | | ALL |
| 0672 | 22 | | GA | | 2-5 | 27-09-14 | D41437J | 17 | | | TB0109Y | A095 | BJ | | ALL |
| 0673 | 22 | | GA | | 2-5 | 27-09-14 | D41437J | 16 | | | TB0109Y | C095 | BJ | | ALL |
| 0674 | 22 | | GA | | 2-1 | 27-61-18 | TB0109Z | 116 | BJ | | D00639A | K15 | | | ALL |
| 0675 | 22 | | GA | | 3-4 | 27-61-17 | TB0109Z | 116 | BJ | | D00637A | K15 | | | ALL |
| 0676 | 22 | | GA | | 2-6 | 27-61-12 | D00635A | C14 | | | D00637A | C15 | | | ALL |
| 0677 | 22 | | GA | | 3-4 | 27-61-12 | D00639A | C15 | | | D00637A | C14 | | | ALL |
| 0678 | 22 | | GA | | 3-10 | 27-61-12 | D00639A | C14 | | | D00635A | C15 | | | ALL |
| 0679 | 22 | | GA | | 2-1 | 27-61-12 | D00639A | H15 | | | TB0109Z | 119 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 65

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|-------------------------------|------------------------|------------------------|-------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W1265 | 286N1265 | E3-1 SHELF (continued) | | | |
| 0680 | 22 GA | 3-4 27-61-12 | D00637A H15 | TB0109Z 119 BJ | ALL |
| 0681 | 22 GA | 2-7 27-61-12 | D41437J 6 | TB0109Z 119 BJ | ALL |
| 0682 | 22 GA | 3-11 27-61-12 | D41838J 4 | TB0109Z 119 BJ | ALL |
| 0683 | 22 GA | 2-8 27-61-12 | D41787J 10 | TB0109Z 119 BJ | ALL |
| 0684 | 22 GA | 3-10 27-61-12 | D00635A H15 | TB0109Z 119 BJ | ALL |
| 0685 | 22 GA | 2-2 22-21-11 | D00349B G08 | D41437J 8 | ALL |
| 0686 | 22 GA | 2-2 22-21-11 | D00349B G07 | D41437J 7 | ALL |
| 0687 | 22 GA | 2-4 22-21-11 | D00349B F07 | TB0109Y A118 BJ | ALL |
| 0688 | 22 GA | 2-7 22-21-11 | D41437J 2 | TB0109Y A118 BJ | ALL |
| 0689 | 22 GA | 2-7 22-21-11 | D41437J 9 | TB0109Y A118 BJ | ALL |
| 0690 | 22 GA | 2-8 22-21-11 | D41787J 11 | TB0109Y A118 BJ | ALL |
| 0691 | 22 GA | 2-1 22-21-11 | D41787J 12 | D00349B F08 | ALL |
| 0693 | 22 GA | 2-4 22-21-11 | D00349B K10 | TB0109Z 116 BJ | ALL |
| 0694 | 22 GA | 2-4 22-22-11 | D41787J 2 | D00705B B05 | ALL |
| 0695 | 22 GA | 2-7 22-24-11 | D41437J 3 | TB0109Y C118 BJ | ALL |
| 0696 | 22 GA | 3-11 22-24-11 | D41838J 2 | TB0109Y C118 BJ | ALL |
| 0697 | 22 GA | 2-8 22-24-11 | D41787J 1 | TB0109Y C118 BJ | ALL |
| 0698 | 22 GA | 2-9 22-24-11 | D00705B C12 | TB0109Y C118 BJ | ALL |
| 0699 | 22 GA | 2-9 27-41-11 | D00705B C11 | TB0109Y A109 BJ | ALL |
| 0700 | 22 GA | 2-9 27-41-11 | D00705B C13 | TB0109Y C109 BJ | ALL |
| 0701 | 22 GA | 2-8 27-41-11 | D41787J 3 | TB0109Y A109 BJ | ALL |
| 0702 | 22 GA | 2-8 27-41-11 | D41787J 4 | TB0109Y C109 BJ | ALL |
| 0703 | 22 GA | 2-7 27-41-11 | D41437J 11 | TB0109Y A109 BJ | ALL |
| 0704 | 22 GA | 2-7 27-41-11 | D41437J 12 | TB0109Y C109 BJ | ALL |
| 0705 | 22 GA | 3-11 27-41-11 | D41838J 7 | TB0109Y C109 BJ | ALL |
| 0706 | 22 GA | 3-11 27-41-11 | D41838J 6 | TB0109Y A109 BJ | ALL |
| 0708 | 22 GA | 2-4 27-21-12 | D41964J 1 | TB0109Y A018 BJ | 001-099 |
| 0708 | 22 GA | 2-4 27-21-12 | D41964J 9 | TB0109Y A018 BJ | 115-199 |
| 0711 | 24 GK | 4-6 34-46-12 | D41437J 13 | TB0109Y C017 BJ | 115-199 |
| 0727 | 24 GK | 2-5 31-31-62 | TB0109Y A015 BJ | TB0109B C026 2 | 001-099 |
| 0728 | 24 GK | 2-5 31-31-62 | TB0109Y C014 BJ | TB0109B C027 2 | 001-099 |
| 0729 | 24 GK | 2-5 31-31-62 | D41399J 15 | TB0109B A026 2 | 001-099 |
| 0730 | 24 GK | 2-5 31-31-62 | D41399J 31 | TB0109B A027 2 | 001-099 |
| 0800 | 22 GA | 1-11 27-41-11 | D00705B G08 | GD01989 DC.. 2 | ALL |
| 0801 | 22 GA | 1-11 27-41-11 | D00705B G09 | GD01989 DC.. 2 | ALL |
| 0802 | 22 GA | 1-11 27-41-11 | D00705B G10 | GD01989 DC.. 2 | ALL |
| 0803 | 22 GA | 1-11 27-41-11 | D00705B G11 | GD01989 DC.. 2 | ALL |
| 0804 | 22 GA | 1-11 27-41-11 | D00705B G12 | GD01989 DC.. 2 | ALL |
| 0805 | 22 GA | 1-11 27-41-11 | D00705B G13 | GD01989 DC.. 2 | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 66

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 0806 | 22 | | GA | | 1-11 | 27-41-11 | D00705B | G14 | | | GD01989 | DC.. | 2 | | ALL |
| 0807 | 22 | | GA | | 1-11 | 27-41-11 | D00705B | G15 | | | GD01989 | DC.. | 2 | | ALL |
| 0900 | 22 | | GA | | 2-4 | 31-51-43 | D41301J | 45 | | | D00637B | H12 | | | ALL |
| 0901 | 22 | | GA | | 3-9 | 31-51-43 | D41301J | 46 | | | GD01980 | DC.. | 2 | | ALL |
| 2001B | 22 | | GB | CT | 2-8 | 27-21-12 | D00705A | K05 | | | D00709A | D04 | | | ALL |
| 2001R | 22 | | GB | CT | 0-0 | 27-21-12 | D00705A | K04 | | | D00709A | D05 | | | ALL |
| 2002B | 22 | | GB | EG | 2-4 | 27-21-12 | TB0109Z | 56 | BJ | | D00709A | A10 | | | ALL |
| 2002R | 22 | | GB | EG | 0-0 | 27-21-12 | TB0109Z | 55 | BJ | | D00709A | A09 | | | ALL |
| 2003B | 22 | | GB | EH | 2-9 | 27-21-22 | D41775J | 24 | | | D00709A | A04 | | | ALL |
| 2003R | 22 | | GB | EH | 0-0 | 27-21-22 | D41775J | 23 | | | D00709A | A05 | | | ALL |
| 2004B | 22 | | GB | AA | 2-10 | 27-61-13 | D00635A | G08 | | | D41761J | 3 | | | ALL |
| 2004R | 22 | | GB | AA | 0-0 | 27-61-13 | D00635A | G09 | | | D41761J | 1 | | | ALL |
| 2005B | 22 | | GB | AB | 2-10 | 27-61-13 | D00635A | K09 | | | D41761J | 5 | | | ALL |
| 2005R | 22 | | GB | AB | 0-0 | 27-61-13 | D00635A | K08 | | | D41761J | 7 | | | ALL |
| 2006B | 22 | | GB | AE | 2-9 | 27-61-13 | D00635A | J11 | | | TB0109Y | C003 | BJ | | ALL |
| 2006R | 22 | | GB | AE | 0-0 | 27-61-13 | D00635A | K11 | | | TB0109Y | A003 | BJ | | ALL |
| 2007B | 22 | | GB | AF | 2-4 | 27-61-13 | D41761J | 8 | | | TB0109Y | C003 | BJ | | ALL |
| 2007R | 22 | | GB | AF | 0-0 | 27-61-13 | D41761J | 9 | | | TB0109Y | A003 | BJ | | ALL |
| 2008B | 22 | | GB | AG | 2-4 | 27-61-13 | D41761J | 18 | | | TB0109Y | C003 | BJ | | ALL |
| 2008R | 22 | | GB | AG | 0-0 | 27-61-13 | D41761J | 19 | | | TB0109Y | A003 | BJ | | ALL |
| 2009B | 22 | | GB | AC | 2-10 | 27-61-13 | D00635A | J09 | | | D41761J | 15 | | | ALL |
| 2009R | 22 | | GB | AC | 0-0 | 27-61-13 | D00635A | J08 | | | D41761J | 17 | | | ALL |
| 2010B | 22 | | GB | AD | 2-10 | 27-61-13 | D00635A | G11 | | | D41761J | 13 | | | ALL |
| 2010R | 22 | | GB | AD | 0-0 | 27-61-13 | D00635A | G10 | | | D41761J | 11 | | | ALL |
| 2011B | 22 | | GB | AH | 2-9 | 27-61-13 | D00635A | J04 | | | TB0109Y | C004 | BJ | | ALL |
| 2011R | 22 | | GB | AH | 0-0 | 27-61-13 | D00635A | J03 | | | TB0109Y | A004 | BJ | | ALL |
| 2012B | 22 | | GB | AJ | 2-9 | 27-61-13 | D00635A | K04 | | | TB0109Y | C005 | BJ | | ALL |
| 2012R | 22 | | GB | AJ | 0-0 | 27-61-13 | D00635A | K03 | | | TB0109Y | A005 | BJ | | ALL |
| 2013B | 22 | | GB | BL | 2-9 | 27-61-13 | TB0109Z | 9 | BJ | | D00635A | J06 | | | ALL |
| 2013R | 22 | | GB | BL | 0-0 | 27-61-13 | TB0109Z | 8 | BJ | | D00635A | K06 | | | ALL |
| 2014B | 22 | | GB | BS | 3-2 | 27-61-17 | TB0109Y | C004 | BJ | | D00637B | J05 | | | ALL |
| 2014R | 22 | | GB | BS | 0-0 | 27-61-17 | TB0109Y | A004 | BJ | | D00637B | J04 | | | ALL |
| 2015B | 22 | | GB | BR | 2-4 | 27-61-17 | TB0109Y | C004 | BJ | | D41761J | 22 | | | 001-099 |
| 2015B | 22 | | GB | BR | 2-4 | 27-61-17 | TB0109Y | C004 | BJ | | D41761J | 31 | | | 115-199 |
| 2015R | 22 | | GB | BR | 0-0 | 27-61-17 | TB0109Y | A004 | BJ | | D41761J | 21 | | | 001-099 |
| 2015R | 22 | | GB | BR | 0-0 | 27-61-17 | TB0109Y | A004 | BJ | | D41761J | 32 | | | 115-199 |
| 2016B | 22 | | GB | BJ | 2-4 | 27-61-17 | TB0109Z | 9 | BJ | | D41761J | 24 | | | 001-099 |
| 2016B | 22 | | GB | BJ | 2-4 | 27-61-17 | TB0109Z | 9 | BJ | | D41761J | 34 | | | 115-199 |
| 2016R | 22 | | GB | BJ | 0-0 | 27-61-17 | TB0109Z | 8 | BJ | | D41761J | 23 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 67

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 2016R | 22 | GB | BJ | | 0-0 | 27-61-17 | TB0109Z | 8 | BJ | | D41761J | 33 | | | 115-199 |
| 2017B | 22 | GB | BK | | 2-4 | 27-61-17 | TB0109Z | 9 | BJ | | D41761J | 26 | | | 001-099 |
| 2017B | 22 | GB | BK | | 2-4 | 27-61-17 | TB0109Z | 9 | BJ | | D41761J | 36 | | | 115-199 |
| 2017R | 22 | GB | BK | | 0-0 | 27-61-17 | TB0109Z | 8 | BJ | | D41761J | 25 | | | 001-099 |
| 2017R | 22 | GB | BK | | 0-0 | 27-61-17 | TB0109Z | 8 | BJ | | D41761J | 35 | | | 115-199 |
| 2018B | 22 | GB | BM | | 3-2 | 27-61-17 | TB0109Y | C005 | BJ | | D00637B | K05 | | | ALL |
| 2018R | 22 | GB | BM | | 0-0 | 27-61-17 | TB0109Y | A005 | BJ | | D00637B | K04 | | | ALL |
| 2019B | 22 | GB | FX | | 2-4 | 27-61-17 | TB0109Y | C005 | BJ | | D41761J | 28 | | | 001-099 |
| 2019B | 22 | GB | FX | | 2-4 | 27-61-17 | TB0109Y | C005 | BJ | | D41761J | 38 | | | 115-199 |
| 2019R | 22 | GB | FX | | 0-0 | 27-61-17 | TB0109Y | A005 | BJ | | D41761J | 27 | | | 001-099 |
| 2019R | 22 | GB | FX | | 0-0 | 27-61-17 | TB0109Y | A005 | BJ | | D41761J | 37 | | | 115-199 |
| 2020B | 22 | GB | BH | | 3-2 | 27-61-17 | TB0109Z | 9 | BJ | | D00637B | J07 | | | ALL |
| 2020R | 22 | GB | BH | | 0-0 | 27-61-17 | TB0109Z | 8 | BJ | | D00637B | K07 | | | ALL |
| 2021B | 22 | GB | BG | | 2-4 | 27-61-17 | TB0109Z | 9 | BJ | | D00701A | C01 | | | ALL |
| 2021R | 22 | GB | BG | | 0-0 | 27-61-17 | TB0109Z | 8 | BJ | | D00701A | A01 | | | ALL |
| 2022B | 22 | GB | BT | | 4-5 | 27-61-18 | TB0109Y | C004 | BJ | | D00639B | J13 | | | ALL |
| 2022R | 22 | GB | BT | | 0-0 | 27-61-18 | TB0109Y | A004 | BJ | | D00639B | J12 | | | ALL |
| 2023B | 22 | GB | BN | | 4-5 | 27-61-18 | TB0109Y | C005 | BJ | | D00639B | K13 | | | ALL |
| 2023R | 22 | GB | BN | | 0-0 | 27-61-18 | TB0109Y | A005 | BJ | | D00639B | K12 | | | ALL |
| 2024B | 22 | GB | BF | | 4-5 | 27-61-18 | TB0109Z | 9 | BJ | | D00639B | J15 | | | ALL |
| 2024R | 22 | GB | BF | | 0-0 | 27-61-18 | TB0109Z | 8 | BJ | | D00639B | K15 | | | ALL |
| 2025B | 22 | GB | EF | | 2-6 | 22-24-11 | D41301J | 44 | | | D00705A | E10 | | | ALL |
| 2025R | 22 | GB | EF | | 0-0 | 22-24-11 | D41301J | 43 | | | D00705A | E09 | | | ALL |
| 2026B | 22 | GB | FY | | 3-8 | 31-31-51 | D41301J | 27 | | | TB0109Y | C016 | BJ | | 010-099 |
| 2026B | 24 | GL | FY | | 3-8 | 31-31-32 | D41301J | 27 | | | TB0109Y | C016 | BJ | | 115-199 |
| 2026R | 22 | GB | FY | | 0-0 | 31-31-51 | D41301J | 26 | | | TB0109Y | A016 | BJ | | 010-099 |
| 2026R | 24 | GL | FY | | 0-0 | 31-31-32 | D41301J | 26 | | | TB0109Y | A016 | BJ | | 115-199 |
| 2028B | 22 | GB | FZ | | 2-2 | 22-21-11 | D00349A | H12 | | | D41789J | 1 | | | ALL |
| 2028R | 22 | GB | FZ | | 0-0 | 22-21-11 | D00349A | K12 | | | D41789J | 2 | | | ALL |
| 2036B | 22 | GB | DC | | 4-2 | 27-09-11 | D00701B | C10 | | | D00703B | A10 | | | ALL |
| 2036R | 22 | GB | DC | | 0-0 | 27-09-11 | D00701B | A10 | | | D00703B | C10 | | | ALL |
| 2101B | 22 | GB | AU | | 2-4 | 27-61-17 | TB0109Y | C041 | BJ | | D00637B | J13 | | | ALL |
| 2101R | 22 | GB | AU | | 0-0 | 27-61-17 | TB0109Y | A041 | BJ | | D00637B | J12 | | | ALL |
| 2102B | 22 | GB | AV | | 2-4 | 27-61-17 | TB0109Y | C043 | BJ | | D00637B | K13 | | | ALL |
| 2102R | 22 | GB | AV | | 0-0 | 27-61-17 | TB0109Y | A043 | BJ | | D00637B | K12 | | | ALL |
| 2103B | 22 | GB | CR | | 2-2 | 27-61-17 | TB0109Z | 50 | BJ | | D00637B | J15 | | | ALL |
| 2103R | 22 | GB | CR | | 0-0 | 27-61-17 | TB0109Z | 49 | BJ | | D00637B | K15 | | | ALL |
| 2104B | 22 | GB | CA | | 2-4 | 27-61-18 | D00639A | G08 | | | D41765J | 3 | | | ALL |
| 2104R | 22 | GB | CA | | 0-0 | 27-61-18 | D00639A | G09 | | | D41765J | 1 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 68

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 2105B | 22 | GB | CB | | 2-4 | 27-61-18 | D00639A | K09 | | | D41765J | 5 | | | ALL |
| 2105R | 22 | GB | CB | | 0-0 | 27-61-18 | D00639A | K08 | | | D41765J | 7 | | | ALL |
| 2106B | 22 | GB | CC | | 3-9 | 27-61-18 | TB0109Y | C044 | BJ | | D00639A | J11 | | | ALL |
| 2106R | 22 | GB | CC | | 0-0 | 27-61-18 | TB0109Y | A044 | BJ | | D00639A | K11 | | | ALL |
| 2107B | 22 | GB | CD | | 4-1 | 27-61-18 | TB0109Y | C044 | BJ | | D41765J | 8 | | | ALL |
| 2107R | 22 | GB | CD | | 0-0 | 27-61-18 | TB0109Y | A044 | BJ | | D41765J | 9 | | | ALL |
| 2108B | 22 | GB | CE | | 4-1 | 27-61-18 | TB0109Y | C044 | BJ | | D41765J | 18 | | | ALL |
| 2108R | 22 | GB | CE | | 0-0 | 27-61-18 | TB0109Y | A044 | BJ | | D41765J | 19 | | | ALL |
| 2109B | 22 | GB | CF | | 2-4 | 27-61-18 | D00639A | J09 | | | D41765J | 15 | | | ALL |
| 2109R | 22 | GB | CF | | 0-0 | 27-61-18 | D00639A | J08 | | | D41765J | 17 | | | ALL |
| 2110B | 22 | GB | CG | | 2-4 | 27-61-18 | D00639A | G11 | | | D41765J | 13 | | | ALL |
| 2110R | 22 | GB | CG | | 0-0 | 27-61-18 | D00639A | G10 | | | D41765J | 11 | | | ALL |
| 2111B | 22 | GB | AW | | 3-9 | 27-61-18 | TB0109Y | C041 | BJ | | D00639A | J04 | | | ALL |
| 2111R | 22 | GB | AW | | 0-0 | 27-61-18 | TB0109Y | A041 | BJ | | D00639A | J03 | | | ALL |
| 2112B | 22 | GB | AX | | 3-9 | 27-61-18 | TB0109Y | C043 | BJ | | D00639A | K04 | | | ALL |
| 2112R | 22 | GB | AX | | 0-0 | 27-61-18 | TB0109Y | A043 | BJ | | D00639A | K03 | | | ALL |
| 2113B | 22 | GB | CS | | 3-7 | 27-61-18 | TB0109Z | 50 | BJ | | D00639A | J06 | | | ALL |
| 2113R | 22 | GB | CS | | 0-0 | 27-61-18 | TB0109Z | 49 | BJ | | D00639A | K06 | | | ALL |
| 2114B | 22 | GB | CU | | 2-11 | 27-21-12 | TB0109Z | 56 | BJ | | D00701A | C12 | | | ALL |
| 2114R | 22 | GB | CU | | 0-0 | 27-21-12 | TB0109Z | 55 | BJ | | D00701A | A12 | | | ALL |
| 2115B | 22 | GB | DE | | 3-1 | 27-21-12 | TB0109Z | 56 | BJ | | D41795J | 2 | | | ALL |
| 2115R | 22 | GB | DE | | 0-0 | 27-21-12 | TB0109Z | 55 | BJ | | D41795J | 1 | | | ALL |
| 2117B | 22 | GB | CZ | | 2-4 | 27-21-12 | TB0109Y | C053 | BJ | | D41779J | 16 | | | ALL |
| 2117R | 22 | GB | CZ | | 0-0 | 27-21-12 | TB0109Y | A053 | BJ | | D41779J | 15 | | | ALL |
| 2118B | 22 | GB | CW | | 2-3 | 27-21-12 | TB0109Z | 56 | BJ | | D00709B | A05 | | | ALL |
| 2118R | 22 | GB | CW | | 0-0 | 27-21-12 | TB0109Z | 55 | BJ | | D00709B | A04 | | | ALL |
| 2119B | 22 | GB | CY | | 2-3 | 27-21-12 | TB0109Y | C053 | BJ | | D00709B | A10 | | | ALL |
| 2119R | 22 | GB | CY | | 0-0 | 27-21-12 | TB0109Y | A053 | BJ | | D00709B | A09 | | | ALL |
| 2120B | 22 | GB | CV | | 2-7 | 27-21-12 | D00705A | K14 | | | D00709B | D10 | | | ALL |
| 2120R | 22 | GB | CV | | 0-0 | 27-21-12 | D00705A | K13 | | | D00709B | D09 | | | ALL |
| 2121B | 22 | GB | AK | | 4-1 | 27-61-13 | D41765J | 22 | | | TB0109Y | C041 | BJ | | ALL |
| 2121R | 22 | GB | AK | | 0-0 | 27-61-13 | D41765J | 21 | | | TB0109Y | A041 | BJ | | ALL |
| 2122B | 22 | GB | AM | | 3-11 | 27-61-13 | D41765J | 24 | | | TB0109Z | 50 | BJ | | ALL |
| 2122R | 22 | GB | AM | | 0-0 | 27-61-13 | D41765J | 23 | | | TB0109Z | 49 | BJ | | ALL |
| 2123B | 22 | GB | AN | | 3-11 | 27-61-13 | D41765J | 26 | | | TB0109Z | 50 | BJ | | ALL |
| 2123R | 22 | GB | AN | | 0-0 | 27-61-13 | D41765J | 25 | | | TB0109Z | 49 | BJ | | ALL |
| 2124B | 22 | GB | AP | | 4-1 | 27-61-13 | D41765J | 28 | | | TB0109Y | C043 | BJ | | ALL |
| 2124R | 22 | GB | AP | | 0-0 | 27-61-13 | D41765J | 27 | | | TB0109Y | A043 | BJ | | ALL |
| 2125B | 22 | GB | AL | | 2-1 | 27-61-13 | TB0109Y | C041 | BJ | | D00635B | J05 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 69

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|------------------------|---------|----------|---------|-------|------|------|--------|---------|------|-------------|------|--------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | | |
| 2125R | 22 | GB | AL | | 0-0 | 27-61-13 | TB0109Y | A041 | BJ | | | D00635B | J04 | | | ALL |
| 2126B | 22 | GB | AR | | 2-1 | 27-61-13 | TB0109Y | C043 | BJ | | | D00635B | K05 | | | ALL |
| 2126R | 22 | GB | AR | | 0-0 | 27-61-13 | TB0109Y | A043 | BJ | | | D00635B | K04 | | | ALL |
| 2127B | 22 | GB | AY | | 2-6 | 27-61-13 | TB0109Z | 50 | BJ | | | D00701B | C01 | | | ALL |
| 2127R | 22 | GB | AY | | 0-0 | 27-61-13 | TB0109Z | 49 | BJ | | | D00701B | A01 | | | ALL |
| 2128B | 22 | GB | AZ | | 2-1 | 27-61-13 | TB0109Z | 50 | BJ | | | D00635B | J07 | | | ALL |
| 2128R | 22 | GB | AZ | | 0-0 | 27-61-13 | TB0109Z | 49 | BJ | | | D00635B | K07 | | | ALL |
| 2129B | 22 | GB | DG | | 2-4 | 22-21-11 | D00349A | D15 | | | | D41795J | 11 | | | ALL |
| 2129R | 22 | GB | DG | | 0-0 | 22-21-11 | D00349A | E14 | | | | D41795J | 10 | | | ALL |
| 2130B | 22 | GB | DJ | | 2-11 | 22-21-11 | D00349A | E15 | | | | TB0109Z | 56 | BJ | | ALL |
| 2130R | 22 | GB | DJ | | 0-0 | 22-21-11 | D00349A | F14 | | | | TB0109Z | 55 | BJ | | ALL |
| 2131B | 22 | GB | DM | | 3-1 | 22-21-11 | D41795J | 16 | | | | TB0109Z | 56 | BJ | | ALL |
| 2131R | 22 | GB | DM | | 0-0 | 22-21-11 | D41795J | 15 | | | | TB0109Z | 55 | BJ | | ALL |
| 2133B | 22 | GB | DD | | 3-1 | 27-21-12 | TB0109Y | C053 | BJ | | | D41795J | 7 | | | ALL |
| 2133R | 22 | GB | DD | | 0-0 | 27-21-12 | TB0109Y | A053 | BJ | | | D41795J | 6 | | | ALL |
| 2201B | 22 | GB | AS | | 2-11 | 27-61-13 | TB0109Y | C081 | BJ | | | D00635B | J13 | | | ALL |
| 2201R | 22 | GB | AS | | 0-0 | 27-61-13 | TB0109Y | A081 | BJ | | | D00635B | J12 | | | ALL |
| 2202B | 22 | GB | AT | | 2-11 | 27-61-13 | TB0109Y | C082 | BJ | | | D00635B | K13 | | | ALL |
| 2202R | 22 | GB | AT | | 0-0 | 27-61-13 | TB0109Y | A082 | BJ | | | D00635B | K12 | | | ALL |
| 2203B | 22 | GB | BA | | 3-9 | 27-61-13 | TB0109Z | 114 | BJ | | | D00635B | J15 | | | ALL |
| 2203R | 22 | GB | BA | | 0-0 | 27-61-13 | TB0109Z | 113 | BJ | | | D00635B | K15 | | | ALL |
| 2204B | 22 | GB | CH | | 2-4 | 27-61-17 | D41763J | 3 | | | | D00637A | G08 | | | ALL |
| 2204R | 22 | GB | CH | | 0-0 | 27-61-17 | D41763J | 1 | | | | D00637A | G09 | | | ALL |
| 2205B | 22 | GB | CJ | | 2-4 | 27-61-17 | D41763J | 5 | | | | D00637A | K09 | | | ALL |
| 2205R | 22 | GB | CJ | | 0-0 | 27-61-17 | D41763J | 7 | | | | D00637A | K08 | | | ALL |
| 2206B | 22 | GB | CK | | 2-6 | 27-61-17 | TB0109Y | C083 | BJ | | | D00637A | J11 | | | ALL |
| 2206R | 22 | GB | CK | | 0-0 | 27-61-17 | TB0109Y | A083 | BJ | | | D00637A | K11 | | | ALL |
| 2207B | 22 | GB | CL | | 2-6 | 27-61-17 | TB0109Y | C083 | BJ | | | D41763J | 8 | | | ALL |
| 2207R | 22 | GB | CL | | 0-0 | 27-61-17 | TB0109Y | A083 | BJ | | | D41763J | 9 | | | ALL |
| 2208B | 22 | GB | CM | | 2-6 | 27-61-17 | TB0109Y | C083 | BJ | | | D41763J | 18 | | | ALL |
| 2208R | 22 | GB | CM | | 0-0 | 27-61-17 | TB0109Y | A083 | BJ | | | D41763J | 19 | | | ALL |
| 2209B | 22 | GB | CN | | 2-4 | 27-61-17 | D00637A | J09 | | | | D41763J | 15 | | | ALL |
| 2209R | 22 | GB | CN | | 0-0 | 27-61-17 | D00637A | J08 | | | | D41763J | 17 | | | ALL |
| 2210B | 22 | GB | CP | | 2-4 | 27-61-17 | D00637A | G11 | | | | D41763J | 13 | | | ALL |
| 2210R | 22 | GB | CP | | 0-0 | 27-61-17 | D00637A | G10 | | | | D41763J | 11 | | | ALL |
| 2211B | 22 | GB | BU | | 2-6 | 27-61-17 | TB0109Y | C081 | BJ | | | D00637A | J04 | | | ALL |
| 2211R | 22 | GB | BU | | 0-0 | 27-61-17 | TB0109Y | A081 | BJ | | | D00637A | J03 | | | ALL |
| 2212B | 22 | GB | BV | | 2-6 | 27-61-17 | TB0109Y | C082 | BJ | | | D00637A | K04 | | | ALL |
| 2212R | 22 | GB | BV | | 0-0 | 27-61-17 | TB0109Y | A082 | BJ | | | D00637A | K03 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 70

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 2213B | 22 | GB | CQ | | 3-4 | 27-61-17 | TB0109Z | 114 | BJ | | D00637A | J06 | | | ALL |
| 2213R | 22 | GB | CQ | | 0-0 | 27-61-17 | TB0109Z | 113 | BJ | | D00637A | K06 | | | ALL |
| 2214B | 22 | GB | BW | | 2-6 | 27-61-18 | TB0109Y | C081 | BJ | | D41763J | 22 | | | 001-099 |
| 2214B | 22 | GB | BW | | 2-6 | 27-61-18 | TB0109Y | C081 | BJ | | D41763J | 31 | | | 115-199 |
| 2214R | 22 | GB | BW | | 0-0 | 27-61-18 | TB0109Y | A081 | BJ | | D41763J | 21 | | | 001-099 |
| 2214R | 22 | GB | BW | | 0-0 | 27-61-18 | TB0109Y | A081 | BJ | | D41763J | 32 | | | 115-199 |
| 2215B | 22 | GB | BX | | 2-10 | 27-61-18 | TB0109Y | C081 | BJ | | D00639B | J05 | | | ALL |
| 2215R | 22 | GB | BX | | 0-0 | 27-61-18 | TB0109Y | A081 | BJ | | D00639B | J04 | | | ALL |
| 2216B | 22 | GB | BB | | 3-4 | 27-61-18 | TB0109Z | 114 | BJ | | D41763J | 24 | | | 001-099 |
| 2216B | 22 | GB | BB | | 3-4 | 27-61-18 | TB0109Z | 114 | BJ | | D41763J | 34 | | | 115-199 |
| 2216R | 22 | GB | BB | | 0-0 | 27-61-18 | TB0109Z | 113 | BJ | | D41763J | 23 | | | 001-099 |
| 2216R | 22 | GB | BB | | 0-0 | 27-61-18 | TB0109Z | 113 | BJ | | D41763J | 33 | | | 115-199 |
| 2217B | 22 | GB | BC | | 3-4 | 27-61-18 | TB0109Z | 114 | BJ | | D41763J | 26 | | | 001-099 |
| 2217B | 22 | GB | BC | | 3-4 | 27-61-18 | TB0109Z | 114 | BJ | | D41763J | 36 | | | 115-199 |
| 2217R | 22 | GB | BC | | 0-0 | 27-61-18 | TB0109Z | 113 | BJ | | D41763J | 25 | | | 001-099 |
| 2217R | 22 | GB | BC | | 0-0 | 27-61-18 | TB0109Z | 113 | BJ | | D41763J | 35 | | | 115-199 |
| 2218B | 22 | GB | BY | | 2-6 | 27-61-18 | TB0109Y | C082 | BJ | | D41763J | 28 | | | 001-099 |
| 2218B | 22 | GB | BY | | 2-6 | 27-61-18 | TB0109Y | C082 | BJ | | D41763J | 38 | | | 115-199 |
| 2218R | 22 | GB | BY | | 0-0 | 27-61-18 | TB0109Y | A082 | BJ | | D41763J | 27 | | | 001-099 |
| 2218R | 22 | GB | BY | | 0-0 | 27-61-18 | TB0109Y | A082 | BJ | | D41763J | 37 | | | 115-199 |
| 2219B | 22 | GB | BD | | 4-1 | 27-61-18 | TB0109Z | 114 | BJ | | D00701B | C05 | | | ALL |
| 2219R | 22 | GB | BD | | 0-0 | 27-61-18 | TB0109Z | 113 | BJ | | D00701B | A05 | | | ALL |
| 2220B | 22 | GB | BE | | 1-11 | 27-61-18 | TB0109Z | 114 | BJ | | D00639B | J07 | | | ALL |
| 2220R | 22 | GB | BE | | 0-0 | 27-61-18 | TB0109Z | 113 | BJ | | D00639B | K07 | | | ALL |
| 2221B | 22 | GB | BZ | | 2-10 | 27-61-18 | TB0109Y | C082 | BJ | | D00639B | K05 | | | ALL |
| 2221R | 22 | GB | BZ | | 0-0 | 27-61-18 | TB0109Y | A082 | BJ | | D00639B | K04 | | | ALL |
| 2501B | 22 | GU | GA | | 2-1 | 22-21-11 | D00349B | K15 | | | D41789J | 5 | | | ALL |
| 2501R | 22 | GU | GA | | 0-0 | 22-21-11 | D00349B | K14 | | | D41789J | 4 | | | ALL |
| 2501Z | | | GA | | 0-0 | 22-21-11 | GD01992 | ST.. | 2 | | D41789J | 7 | | | ALL |
| 3001B | 22 | GC | EJ | | 2-4 | 27-21-12 | TB0109Y | A051 | BJ | | D00709A | B09 | | | ALL |
| 3001R | 22 | GC | EJ | | 0-0 | 27-21-12 | TB0109Y | A052 | BJ | | D00709A | B08 | | | ALL |
| 3001Y | 22 | GC | EJ | | 0-0 | 27-21-12 | TB0109Y | C051 | BJ | | D00709A | B10 | | | ALL |
| 3002B | 22 | GC | EK | | 3-4 | 27-41-11 | D00701A | H06 | | | D00705A | H05 | | | ALL |
| 3002R | 22 | GC | EK | | 0-0 | 27-41-11 | D00701A | H05 | | | D00705A | H04 | | | ALL |
| 3002Y | 22 | GC | EK | | 0-0 | 27-41-11 | D00701A | G05 | | | D00705A | H06 | | | ALL |
| 3003B | 22 | GC | EL | | 3-4 | 27-41-11 | D00701A | G06 | | | D00705A | J05 | | | ALL |
| 3003R | 22 | GC | EL | | 0-0 | 27-41-11 | D00701A | H07 | | | D00705A | J04 | | | ALL |
| 3003Y | 22 | GC | EL | | 0-0 | 27-41-11 | D00701A | G07 | | | D00705A | J06 | | | ALL |
| 3004B | 22 | GC | EP | | 3-1 | 27-41-11 | D00703A | H06 | | | D00705A | F05 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 71

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 3004R | 22 | GC | EP | | 0-0 | 27-41-11 | D00703A | H05 | | | D00705A | F04 | | | ALL |
| 3004Y | 22 | GC | EP | | 0-0 | 27-41-11 | D00703A | G05 | | | D00705A | F06 | | | ALL |
| 3005B | 22 | GC | EQ | | 3-1 | 27-41-11 | D00703A | G06 | | | D00705A | G05 | | | ALL |
| 3005R | 22 | GC | EQ | | 0-0 | 27-41-11 | D00703A | H07 | | | D00705A | G04 | | | ALL |
| 3005Y | 22 | GC | EQ | | 0-0 | 27-41-11 | D00703A | G07 | | | D00705A | G06 | | | ALL |
| 3006B | 22 | GC | FP | | 3-9 | 22-21-11 | D00349A | K02 | | | D00701A | K06 | | | ALL |
| 3006R | 22 | GC | FP | | 0-0 | 22-21-11 | D00349A | K01 | | | D00701A | K05 | | | ALL |
| 3006Y | 22 | GC | FP | | 0-0 | 22-21-11 | D00349A | J01 | | | D00701A | J05 | | | ALL |
| 3007B | 22 | GC | FQ | | 3-9 | 22-21-11 | D00349A | H01 | | | D00701A | J06 | | | ALL |
| 3007R | 22 | GC | FQ | | 0-0 | 22-21-11 | D00349A | J02 | | | D00701A | K07 | | | ALL |
| 3007Y | 22 | GC | FQ | | 0-0 | 22-21-11 | D00349A | H02 | | | D00701A | J07 | | | ALL |
| 3008B | 22 | GC | FR | | 2-8 | 22-21-11 | D00349A | G02 | | | D00703A | K06 | | | ALL |
| 3008R | 22 | GC | FR | | 0-0 | 22-21-11 | D00349A | G01 | | | D00703A | K05 | | | ALL |
| 3008Y | 22 | GC | FR | | 0-0 | 22-21-11 | D00349A | F01 | | | D00703A | J05 | | | ALL |
| 3009B | 22 | GC | FS | | 2-8 | 22-21-11 | D00349A | E01 | | | D00703A | J06 | | | ALL |
| 3009R | 22 | GC | FS | | 0-0 | 22-21-11 | D00349A | F02 | | | D00703A | K07 | | | ALL |
| 3009Y | 22 | GC | FS | | 0-0 | 22-21-11 | D00349A | E02 | | | D00703A | J07 | | | ALL |
| 3101B | 22 | GC | CX | | 2-3 | 27-21-12 | TB0109Y | A051 | BJ | | D00709B | B05 | | | ALL |
| 3101R | 22 | GC | CX | | 0-0 | 27-21-12 | TB0109Y | A052 | BJ | | D00709B | B06 | | | ALL |
| 3101Y | 22 | GC | CX | | 0-0 | 27-21-12 | TB0109Y | C051 | BJ | | D00709B | B04 | | | ALL |
| 3103B | 22 | GC | DB | | 3-1 | 27-21-12 | TB0109Y | A051 | BJ | | D41795J | 4 | | | ALL |
| 3103R | 22 | GC | DB | | 0-0 | 27-21-12 | TB0109Y | A052 | BJ | | D41795J | 3 | | | ALL |
| 3103Y | 22 | GC | DB | | 0-0 | 27-21-12 | TB0109Y | C051 | BJ | | D41795J | 5 | | | ALL |
| 3104B | 22 | GC | DH | | 2-4 | 22-21-11 | D00349A | C14 | | | D41795J | 13 | | | ALL |
| 3104R | 22 | GC | DH | | 0-0 | 22-21-11 | D00349A | D14 | | | D41795J | 12 | | | ALL |
| 3104Y | 22 | GC | DH | | 0-0 | 22-21-11 | D00349A | C15 | | | D41795J | 14 | | | ALL |
| 3105B | 22 | GC | EM | | 3-2 | 27-41-11 | D00701A | H09 | | | D00705B | K03 | | | ALL |
| 3105R | 22 | GC | EM | | 0-0 | 27-41-11 | D00701A | H08 | | | D00705B | K02 | | | ALL |
| 3105Y | 22 | GC | EM | | 0-0 | 27-41-11 | D00701A | G08 | | | D00705B | K04 | | | ALL |
| 3106B | 22 | GC | FN | | 3-2 | 27-41-11 | D00701A | G09 | | | D00705B | J03 | | | ALL |
| 3106R | 22 | GC | FN | | 0-0 | 27-41-11 | D00701A | H10 | | | D00705B | J02 | | | ALL |
| 3106Y | 22 | GC | FN | | 0-0 | 27-41-11 | D00701A | G10 | | | D00705B | J04 | | | ALL |
| 3107B | 22 | GC | ER | | 3-0 | 27-41-11 | D00703A | H09 | | | D00705B | H03 | | | ALL |
| 3107R | 22 | GC | ER | | 0-0 | 27-41-11 | D00703A | H08 | | | D00705B | H02 | | | ALL |
| 3107Y | 22 | GC | ER | | 0-0 | 27-41-11 | D00703A | G08 | | | D00705B | H04 | | | ALL |
| 3108B | 22 | GC | ES | | 3-0 | 27-41-11 | D00703A | G09 | | | D00705B | G03 | | | ALL |
| 3108R | 22 | GC | ES | | 0-0 | 27-41-11 | D00703A | H10 | | | D00705B | G02 | | | ALL |
| 3108Y | 22 | GC | ES | | 0-0 | 27-41-11 | D00703A | G10 | | | D00705B | G04 | | | ALL |
| 3109B | 22 | GC | FT | | 3-8 | 22-21-11 | D00349B | K02 | | | D00701A | K09 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 72

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 3109R | 22 | GC | FT | | 0-0 | 22-21-11 | D00349B | K01 | | | D00701A | K08 | | | ALL |
| 3109Y | 22 | GC | FT | | 0-0 | 22-21-11 | D00349B | J01 | | | D00701A | J08 | | | ALL |
| 3110B | 22 | GC | FU | | 3-8 | 22-21-11 | D00349B | H01 | | | D00701A | J09 | | | ALL |
| 3110R | 22 | GC | FU | | 0-0 | 22-21-11 | D00349B | J02 | | | D00701A | K10 | | | ALL |
| 3110Y | 22 | GC | FU | | 0-0 | 22-21-11 | D00349B | H02 | | | D00701A | J10 | | | ALL |
| 3111B | 22 | GC | FV | | 2-6 | 22-21-11 | D00349B | G02 | | | D00703A | K09 | | | ALL |
| 3111R | 22 | GC | FV | | 0-0 | 22-21-11 | D00349B | G01 | | | D00703A | K08 | | | ALL |
| 3111Y | 22 | GC | FV | | 0-0 | 22-21-11 | D00349B | F01 | | | D00703A | J08 | | | ALL |
| 3112B | 22 | GC | FW | | 2-6 | 22-21-11 | D00349B | E01 | | | D00703A | J09 | | | ALL |
| 3112R | 22 | GC | FW | | 0-0 | 22-21-11 | D00349B | F02 | | | D00703A | K10 | | | ALL |
| 3112Y | 22 | GC | FW | | 0-0 | 22-21-11 | D00349B | E02 | | | D00703A | J10 | | | ALL |
| 5001B | 24 | G2 | DZ | | 2-6 | 22-22-11 | D41301J | 6 | | | D00705A | D08 | | | ALL |
| 5001R | 24 | G2 | DZ | | 0-0 | 22-22-11 | D41301J | 5 | | | D00705A | D07 | | | ALL |
| 5001Z | | | DZ | | 0-0 | 22-22-11 | D41301J | 7 | | | GD01989 | ST.. | 2 | | ALL |
| 5004B | 24 | G2 | EA | | 3-8 | 22-24-11 | D41301J | 17 | | | TB0109Y | C013 | BJ | | ALL |
| 5004R | 24 | G2 | EA | | 0-0 | 22-24-11 | D41301J | 16 | | | TB0109Y | A013 | BJ | | ALL |
| 5004Z | | | EA | | 0-0 | 22-24-11 | D41301J | 18 | | | TB0109Y | | | AE | ALL |
| 5005B | 24 | G2 | EB | | 3-8 | 22-24-11 | D00705A | D12 | | | TB0109Y | C013 | BJ | | ALL |
| 5005R | 24 | G2 | EB | | 0-0 | 22-24-11 | D00705A | D11 | | | TB0109Y | A013 | BJ | | ALL |
| 5005Z | | | EB | | 0-0 | 22-24-11 | D00705A | DED | | | TB0109Y | | | AE | ALL |
| 5007B | 24 | G2 | DP | | 4-2 | 22-21-11 | D00349A | K05 | | | TB0109Y | C011 | BJ | | ALL |
| 5007R | 24 | G2 | DP | | 0-0 | 22-21-11 | D00349A | K04 | | | TB0109Y | A011 | BJ | | ALL |
| 5007Z | | | DP | | 0-0 | 22-21-11 | D00349A | DED | | | TB0109Y | | | AB | ALL |
| 5008B | 24 | G2 | DQ | | 3-8 | 22-21-11 | D41301J | 20 | | | TB0109Y | C011 | BJ | | ALL |
| 5008R | 24 | G2 | DQ | | 0-0 | 22-21-11 | D41301J | 19 | | | TB0109Y | A011 | BJ | | ALL |
| 5008Z | | | DQ | | 0-0 | 22-21-11 | D41301J | 21 | | | TB0109Y | | | AB | ALL |
| 5010B | 24 | G2 | DL | | 4-2 | 22-21-11 | D00349A | K15 | | | TB0109Y | C013 | BJ | | ALL |
| 5010R | 24 | G2 | DL | | 0-0 | 22-21-11 | D00349A | K14 | | | TB0109Y | A013 | BJ | | ALL |
| 5010Z | | | DL | | 0-0 | 22-21-11 | D00349A | DED | | | TB0109Y | | | AE | ALL |
| 5101B | 24 | G2 | ED | | 2-9 | 22-24-11 | D41353J | 2 | | | TB0109Y | C059 | BJ | | ALL |
| 5101R | 24 | G2 | ED | | 0-0 | 22-24-11 | D41353J | 1 | | | TB0109Y | A059 | BJ | | ALL |
| 5101Z | | | ED | | 0-0 | 22-24-11 | D41353J | 3 | | | TB0109Y | | | AF | ALL |
| 5102B | 24 | G2 | EE | | 2-6 | 22-24-11 | D00705A | A12 | | | TB0109Y | C059 | BJ | | ALL |
| 5102R | 24 | G2 | EE | | 0-0 | 22-24-11 | D00705A | A11 | | | TB0109Y | A059 | BJ | | ALL |
| 5102Z | | | EE | | 0-0 | 22-24-11 | D00705A | DED | | | TB0109Y | | | AF | ALL |
| 5103B | 24 | G2 | DV | | 3-5 | 22-21-11 | D00349B | K05 | | | D41353J | 4 | | | ALL |
| 5103R | 24 | G2 | DV | | 0-0 | 22-21-11 | D00349B | K04 | | | D41353J | 5 | | | ALL |
| 5103Z | | | DV | | 0-0 | 22-21-11 | D41353J | 6 | | | GD01992 | ST.. | 2 | | ALL |
| 5104B | 24 | G2 | DK | | 2-11 | 22-21-11 | D00349A | A15 | | | TB0109Y | C059 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 73

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1265 | 286N1265 | | | E3-1 SHELF (continued) | | | | | | | | | | | |
| 5104R | 24 | G2 | DK | | 0-0 | 22-21-11 | D00349A | A14 | | | TB0109Y | A059 | BJ | | ALL |
| 5104Z | | | DK | | 0-0 | 22-21-11 | D00349A | DED | | | TB0109Y | | | AF | ALL |
| 5201B | 24 | G2 | DS | | 1-11 | 22-21-11 | D00349B | A15 | | | TB0109Y | C087 | BJ | | ALL |
| 5201R | 24 | G2 | DS | | 0-0 | 22-21-11 | D00349B | A14 | | | TB0109Y | A087 | BJ | | ALL |
| 5201Z | | | DS | | 0-0 | 22-21-11 | D00349B | DED | | | TB0109Y | | | AC | ALL |
| 5202B | 24 | G2 | DT | | 4-2 | 22-21-11 | D41399J | 9 | | | TB0109Y | C087 | BJ | | ALL |
| 5202R | 24 | G2 | DT | | 0-0 | 22-21-11 | D41399J | 8 | | | TB0109Y | A087 | BJ | | ALL |
| 5202Z | | | DT | | 0-0 | 22-21-11 | D41399J | 10 | | | TB0109Y | | | AC | ALL |
| 5203B | 24 | G2 | DU | | 3-11 | 22-21-11 | D41783J | 18 | | | TB0109Y | C087 | BJ | | ALL |
| 5203R | 24 | G2 | DU | | 0-0 | 22-21-11 | D41783J | 17 | | | TB0109Y | A087 | BJ | | ALL |
| 5203Z | | | DU | | 0-0 | 22-21-11 | D41783J | 19 | | | TB0109Y | | | AC | ALL |
| 5204B | 24 | G2 | DW | | 4-2 | 22-22-11 | D41399J | 4 | | | TB0109Y | C089 | BJ | | ALL |
| 5204R | 24 | G2 | DW | | 0-0 | 22-22-11 | D41399J | 3 | | | TB0109Y | A089 | BJ | | ALL |
| 5204Z | | | DW | | 0-0 | 22-22-11 | D41399J | 5 | | | TB0109Y | | | AD | ALL |
| 5205B | 24 | G2 | DX | | 2-4 | 22-22-11 | D00705B | K15 | | | TB0109Y | C089 | BJ | | ALL |
| 5205R | 24 | G2 | DX | | 0-0 | 22-22-11 | D00705B | K14 | | | TB0109Y | A089 | BJ | | ALL |
| 5205Z | | | DX | | 0-0 | 22-22-11 | D00705B | DED | | | TB0109Y | | | AD | ALL |
| 5206B | 24 | G2 | DY | | 3-11 | 22-22-11 | D41783J | 7 | | | TB0109Y | C089 | BJ | | ALL |
| 5206R | 24 | G2 | DY | | 0-0 | 22-22-11 | D41783J | 8 | | | TB0109Y | A089 | BJ | | ALL |
| 5206Z | | | DY | | 0-0 | 22-22-11 | D41783J | 9 | | | TB0109Y | | | AD | ALL |
| FRAB | | | | | 0-0 | 22-21-11 | GD01982 | ST.. | 2 | | TB0109Y | | | AB | ALL |
| FRAC | | | | | 0-0 | 22-21-11 | GD01991 | ST.. | 2 | | TB0109Y | | | AC | ALL |
| FRAD | | | | | 0-0 | 22-22-11 | GD01991 | ST.. | 2 | | TB0109Y | | | AD | ALL |
| FRAE | | | | | 0-0 | 22-24-11 | GD01982 | ST.. | 2 | | TB0109Y | | | AE | ALL |
| FRAF | | | | | 0-0 | 22-24-11 | GD01986 | ST.. | 2 | | TB0109Y | | | AF | ALL |

WIRE LIST

D280N032

91-21-11

Section W1260

Page 74 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) | | | | | | | | | | | |
| 0005 | 24 | | GK | | 9-0 | 21-25-11 | D05188 | | 2 | | D41856J | | 53 | | 001-099 |
| 0005 | 24 | | GK | | 7-0 | 21-25-11 | D05188 | | 2 | | D41856J | | 53 | | 115-199 |
| 0009 | 24 | | GK | | 5-0 | 23-31-41 | D41739J | | 29 | | D40410J | | 15 | | 001-099 |
| 0009 | 24 | | GK | | 4-0 | 23-31-41 | D41739J | | 29 | | D40410J | | 15 | | 115-199 |
| 0010 | 20 | | GK | | 5-0 | 24-51-24 | K00120 | | 13 | C | GD01716 | DC.. | F | | 001-099 |
| 0010 | 20 | | GK | | 4-0 | 24-51-24 | K00120 | | 13 | C | GD01716 | DC.. | F | | 115-199 |
| 0011 | 20 | | GK | | 5-0 | 24-51-24 | K10298 | | 14 | C | D41856J | | 40 | | 001-099 |
| 0011 | 20 | | GK | | 4-0 | 24-51-24 | K10298 | | 14 | C | D41856J | | 40 | | 115-199 |
| 0012 | 20 | | GK | | 5-0 | 24-51-24 | K00120 | | X1 | C | D41856J | | 31 | | 001-099 |
| 0012 | 20 | | GK | | 4-0 | 24-51-24 | K00120 | | X1 | C | D41856J | | 31 | | 115-199 |
| 0013 | 20 | | GK | | 4-0 | 24-51-24 | K00120 | | X2 | C | D41909J | | 20 | | ALL |
| 0014 | 20 | | GK | | 5-0 | 24-51-51 | K00102 | | X1 | C | D40978J | | 10 | | 115-199 |
| 0015 | 20 | | GK | | 5-0 | 24-51-51 | K00102 | | X1 | C | D40978J | | 9 | | 115-199 |
| 0016 | 20 | | GK | | 4-0 | 24-51-51 | K00102 | | X2 | C | GD01716 | DC.. | F | | 115-199 |
| 0017 | 24 | | GK | | 7-0 | 24-51-71 | D41748J | | 9 | | TB0173Y | C001 | BJ | | 001-099 |
| 0017 | 24 | | GK | | 5-0 | 24-51-71 | D41748J | | 9 | | TB0178Y | C003 | BJ | | 115-199 |
| 0018 | 24 | | GK | | 7-0 | 24-51-71 | D41748J | | 2 | | TB0173Y | C001 | BJ | | 001-099 |
| 0018 | 24 | | GK | | 5-0 | 24-51-71 | D41748J | | 2 | | TB0178Y | C003 | BJ | | 115-199 |
| 0021 | 20 | | GK | | 5-0 | 28-25-11 | D41546J | | 51 | | D42176J | | 16 | | 115-199 |
| 0022 | 24 | | GK | | 5-0 | 26-11-21 | D41858J | | 27 | | D42010J | | 19 | | 001-099 |
| 0022 | 24 | | GK | | 4-0 | 26-11-21 | D41858J | | 27 | | D42010J | | 19 | | 115-199 |
| 0023 | 24 | | GK | | 5-0 | 26-11-21 | D40570J | | 46 | | D42008J | | 9 | | ALL |
| 0024 | 24 | | GK | | 5-0 | 30-33-11 | D41032J | | 23 | | TB0178Y | C010 | BJ | | 115-199 |
| 0025 | 24 | | GK | | 8-0 | 30-33-11 | D41032J | | 24 | | D04246 | | 2 | | 001-099 |
| 0025 | 24 | | GK | | 7-0 | 30-33-11 | D41032J | | 24 | | D04246 | | 2 | | 115-199 |
| 0026 | 22 | | GK | | 5-0 | 31-31-01 | D41739J | | 5 | | TB0178Y | C039 | BJ | | 001-099 |
| 0026 | 22 | | GK | | 5-0 | 31-31-13 | D41739J | | 5 | | TB0178Y | C011 | BJ | | 115-199 |
| 0027 | 24 | | GK | | 6-0 | 31-51-41 | D40570J | | 16 | | D41739J | | 32 | | 001-099 |
| 0027 | 24 | | GK | | 5-0 | 31-51-41 | D40570J | | 16 | | D41739J | | 32 | | 115-199 |
| 0028 | 20 | | GK | | 4-0 | 33-24-11 | D41302J | | 14 | | SM00003 | | WI | | 001-099 |
| 0028 | 20 | | GK | | 5-0 | 33-24-11 | D41302J | | 14 | | TB0178Y | A012 | BJ | | 115-199 |
| 0029 | 20 | | GK | | 4-0 | 33-24-11 | D41408J | | 5 | | SM00003 | | WI | | 001-099 |
| 0029 | 20 | | GK | | 5-0 | 33-24-11 | D41408J | | 5 | | TB0178Y | A012 | BJ | | 115-199 |
| 0030 | 20 | | GK | | 4-0 | 33-24-11 | D40496J | | 17 | | SM00003 | | WI | | 001-099 |
| 0030 | 20 | | GK | | 5-0 | 33-24-11 | D40496J | | 31 | | TB0178Y | A012 | BJ | | 115-199 |
| 0031 | 22 | | GK | | 6-0 | 33-24-11 | D40410J | | 7 | | D41408J | | 3 | | 001-099 |
| 0031 | 22 | | GK | | 5-0 | 33-24-11 | D40410J | | 7 | | D41408J | | 3 | | 115-199 |
| 0032 | 16 | | GK | | 6-0 | 33-24-11 | D40410J | | 1 | 16 | D41408J | | 1 | | 001-099 |
| 0032 | 16 | | GK | | 5-0 | 33-24-11 | D40410J | | 1 | 16 | D41408J | | 2 | 16 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 1

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0033 | 24 | | GK | | 5-0 | 26-16-11 | D41858J | 28 | | | D41994J | 25 | | | 001-099 |
| 0033 | 24 | | GK | | 4-0 | 26-16-11 | D41858J | 28 | | | D41994J | 25 | | | 115-199 |
| 0034 | 22 | | GK | | 7-0 | 29-11-21 | D40594J | 15 | | | D42010J | 23 | | | 001-099 |
| 0034 | 22 | | GK | | 6-0 | 29-11-21 | D40594J | 15 | | | D42010J | 23 | | | 115-199 |
| 0035 | 22 | | GK | | 5-0 | 33-25-21 | D40410J | 2 | | | D41739J | 19 | | | 001-099 |
| 0036 | 22 | | GK | | 7-0 | 31-31-01 | TB0170Y | A004 | BJ | | TB0178Y | A026 | BJ | | 001-099 |
| 0036 | 22 | | GK | | 9-0 | 31-31-13 | TB0170Y | A004 | BJ | | TB0178Z | 26 | BJ | | 115-199 |
| 0037 | 22 | | GK | | 4-0 | 33-26-11 | D40978J | 12 | | | SM00004 | | WI | | 001-099 |
| 0037 | 20 | | GK | | 5-0 | 33-26-11 | D40978J | 12 | | | TB0178Y | A015 | BJ | | 115-199 |
| 0038 | 22 | | GK | | 4-0 | 33-26-11 | D40496J | 4 | | | SM00004 | | WI | | 001-099 |
| 0038 | 22 | | GK | | 5-0 | 33-26-11 | D40496J | 4 | | | TB0178Y | A015 | BJ | | 115-199 |
| 0039 | 22 | | GK | | 4-0 | 33-26-11 | D41302J | 3 | | | SM00004 | | WI | | 001-099 |
| 0039 | 22 | | GK | | 5-0 | 33-26-11 | D41302J | 3 | | | TB0178Y | A015 | BJ | | 115-199 |
| 0040 | 16 | | GK | | 4-0 | 33-26-11 | D40496J | 3 | 16 | | SM00008 | | WI | | 001-099 |
| 0040 | 22 | | GK | | 5-0 | 33-26-11 | D40496J | 3 | | | TB0178Z | 17 | BJ | | 115-199 |
| 0041 | 16 | | GK | | 7-0 | 33-26-11 | D40718J | 50 | 16 | | D07080 | D3 | | | 001-099 |
| 0041 | 22 | | GK | | 8-0 | 33-26-11 | D40718J | 50 | | | D07080 | D3 | | | 115-199 |
| 0042 | 16 | | GK | | 4-0 | 33-26-11 | D41302J | 5 | 16 | | SM00008 | | WI | | 001-099 |
| 0042 | 22 | | GK | | 5-0 | 33-26-11 | D41302J | 5 | | | TB0178Z | 17 | BJ | | 115-199 |
| 0043 | 16 | | GK | | 4-0 | 33-26-21 | D41302J | 7 | 16 | | SM00008 | | WI | | 001-099 |
| 0043 | 22 | | GK | | 5-0 | 33-26-21 | D41302J | 7 | | | TB0178Z | 17 | BJ | | 115-199 |
| 0044 | 16 | | GK | | 4-0 | 33-26-21 | D40496J | 12 | 16 | | SM00008 | | WI | | 001-099 |
| 0044 | 22 | | GK | | 5-0 | 33-26-21 | D40496J | 12 | | | TB0178Z | 17 | BJ | | 115-199 |
| 0045 | 22 | | GK | | 4-0 | 33-26-31 | D41302J | 6 | | | SM00006 | | WI | | 001-099 |
| 0045 | 22 | | GK | | 5-0 | 33-26-31 | D41302J | 6 | | | TB0178Y | A016 | BJ | | 115-199 |
| 0046 | 22 | | GK | | 5-0 | 33-26-31 | D40496J | 23 | | | D40718J | 53 | | | 001-099 |
| 0046 | 22 | | GK | | 5-0 | 33-26-31 | D40496J | 26 | | | D40718J | 53 | | | 115-199 |
| 0047 | 22 | | GK | | 4-0 | 33-26-31 | D40496J | 19 | | | SM00006 | | WI | | 001-099 |
| 0047 | 22 | | GK | | 5-0 | 33-26-31 | D40496J | 22 | | | TB0178Y | A016 | BJ | | 115-199 |
| 0048 | 22 | | GK | | 4-0 | 33-26-31 | D40718J | 46 | | | SM00006 | | WI | | 001-099 |
| 0048 | 22 | | GK | | 4-0 | 33-26-31 | D40718J | 46 | | | TB0178Y | A016 | BJ | | 115-199 |
| 0049 | 22 | | GK | | 5-0 | 33-27-11 | D41748J | 12 | | | TB0178Z | 18 | BJ | | 115-199 |
| 0050 | 22 | | GK | | 5-0 | 33-27-21 | D41748J | 15 | | | TB0178Z | 18 | BJ | | 115-199 |
| 0051 | 22 | | GK | | 5-0 | 33-27-31 | D40496J | 9 | | | TB0178Z | 18 | BJ | | 115-199 |
| 0052 | 22 | | GK | | 4-0 | 33-27-31 | D40496J | 11 | | | D41408J | 12 | | | 115-199 |
| 0053 | 22 | | GK | | 4-0 | 33-27-31 | D40496J | 10 | | | D41408J | 11 | | | 115-199 |
| 0054 | 20 | | GK | | 4-0 | 33-44-11 | D41302J | 1 | | | SM00005 | | WI | | 001-099 |
| 0054 | 20 | | GK | | 5-0 | 33-44-11 | D41302J | 1 | | | TB0178Y | C015 | BJ | | 115-199 |
| 0055 | 20 | | GK | | 5-0 | 33-44-11 | D40064J | 6 | | | SM00005 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 2

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0055 | 20 | | GK | | 5-0 | 33-44-11 | TB0178Y | C015 | BJ | | D40064J | 6 | | | 115-199 |
| 0056 | 20 | | GK | | 4-0 | 33-44-11 | D40594J | 1 | | | SM00005 | | WI | | 001-099 |
| 0056 | 20 | | GK | | 5-0 | 33-44-11 | D40594J | 1 | | | TB0178Y | C015 | BJ | | 115-199 |
| 0057 | 20 | | GK | | 3-0 | 33-44-21 | D41728J | 10 | | | SM00007 | | WI | | 001-099 |
| 0057 | 20 | | GK | | 5-0 | 33-44-21 | D41728J | 10 | | | TB0178Y | C016 | BJ | | 115-199 |
| 0058 | 20 | | GK | | 4-0 | 33-44-21 | D41852J | 2 | | | SM00007 | | WI | | 001-099 |
| 0058 | 20 | | GK | | 5-0 | 33-44-21 | D41852J | 2 | | | TB0178Y | C016 | BJ | | 115-199 |
| 0059 | 20 | | GK | | 4-0 | 33-44-21 | D41852J | 1 | | | SM00007 | | WI | | 001-099 |
| 0059 | 20 | | GK | | 5-0 | 33-44-21 | D41852J | 1 | | | TB0178Y | C016 | BJ | | 115-199 |
| 0060 | 24 | | GK | | 5-0 | 33-51-11 | D40490J | 2 | | | D41302J | 13 | | | 001-099 |
| 0060 | 18 | | GK | | 3-0 | 33-51-11 | D40490J | 2 | | | D41302J | 13 | 18 | | 115-199 |
| 0061 | 24 | | GK | | 5-0 | 33-51-11 | D41302J | 11 | | | D40490J | 3 | | | 001-099 |
| 0061 | 18 | | GK | | 3-0 | 33-51-11 | D40490J | 3 | | | D41302J | 11 | 18 | | 115-199 |
| 0062 | 24 | | GK | | 5-0 | 33-51-11 | D40490J | 4 | | | D41302J | 9 | | | 001-099 |
| 0062 | 18 | | GK | | 3-0 | 33-51-11 | D40490J | 4 | | | D41302J | 9 | 18 | | 115-199 |
| 0063 | 24 | | GK | | 5-0 | 33-51-11 | D40490J | 5 | | | D41302J | 8 | | | 001-099 |
| 0063 | 18 | | GK | | 3-0 | 33-51-11 | D40490J | 5 | | | D41302J | 8 | 18 | | 115-199 |
| 0064 | 22 | | GK | | 8-0 | 33-51-11 | D07080 | A2 | | * | D41302J | 10 | | | 001-099 |
| 0064 | 22 | | GK | | 9-0 | 33-51-11 | D07080 | A2 | | * | D41302J | 10 | | | 115-199 |
| 0065 | 22 | | GK | | 8-0 | 33-51-11 | D07080 | B2 | | | D41302J | 12 | | | 001-099 |
| 0065 | 22 | | GK | | 9-0 | 33-51-11 | D07080 | B2 | | | D41302J | 12 | | | 115-199 |
| 0066 | 20 | | GK | | 6-0 | 34-12-21 | T00140 | LV | D | | D41487J | 26 | | | ALL |
| 0067 | 20 | | GK | | 6-0 | 34-12-21 | T00140 | G | D | | D41487J | 27 | | | ALL |
| 0068 | 24 | | GK | | 6-0 | 34-12-21 | T00140 | HV | D | | D41487J | 28 | | | ALL |
| 0069 | 24 | | GK | | 6-0 | 34-33-31 | D40570J | 5 | | | D41495J | 7 | | | 001-099 |
| 0069 | 24 | | GK | | 5-0 | 34-33-31 | D40570J | 5 | | | D41495J | 7 | | | 115-199 |
| 0070 | 24 | | GK | | 5-0 | 36-11-22 | D40718J | 28 | | | D40064J | 48 | | | 001-099 |
| 0070 | 24 | | GK | | 4-0 | 36-11-22 | D40718J | 28 | | | D40064J | 48 | | | 115-199 |
| 0071 | 24 | | GK | | 6-0 | 29-35-11 | D41030J | 50 | | | TB0178A | A017 | 2 | | 001-099 |
| 0071 | 24 | | GK | | 7-0 | 29-35-11 | D41030J | 50 | | | TB0174C | A024 | 2 | | 115-199 |
| 0072 | 24 | | GK | | 5-0 | 36-21-11 | D40718J | 20 | | | D40064J | 30 | | | 001-099 |
| 0072 | 24 | | GK | | 4-0 | 36-21-11 | D40718J | 20 | | | D40064J | 30 | | | 115-199 |
| 0073 | 22 | | GK | | 6-0 | 38-13-11 | D40496J | 14 | | | D41032J | 27 | | | 001-099 |
| 0073 | 18 | | GK | | 6-0 | 38-13-11 | D40496J | 21 | 18 | | D41032J | 27 | 18 | | 115-199 |
| 0074 | 22 | | GK | | 6-0 | 38-13-11 | D40496J | 16 | | | D41032J | 26 | | | 001-099 |
| 0074 | 18 | | GK | | 6-0 | 38-13-11 | D40496J | 23 | 18 | | D41032J | 26 | 18 | | 115-199 |
| 0075 | 22 | | GK | | 4-0 | 38-14-11 | D40186J | 1 | | | SM00032 | | WI | | 001-099 |
| 0075 | 22 | | GK | | 5-0 | 38-14-11 | D40186J | 1 | | | D40718J | 41 | | | 115-199 |
| 0076 | 22 | | GK | | 5-0 | 38-14-11 | D40186J | 2 | | | D41302J | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 3

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0076 | 22 | | GK | | 5-0 | 38-14-11 | D40186J | | | 2 | TB0178Y | A028 | BJ | | 115-199 |
| 0077 | 22 | | GK | | 5-0 | 38-14-11 | D41302J | | | 18 | TB0178Y | A028 | BJ | | 115-199 |
| 0078 | 20 | | GK | | 5-0 | 38-14-11 | D40186J | | | 5 | TB0178Y | A028 | BJ | | 115-199 |
| 0079 | 22 | | GK | | 6-0 | 38-14-11 | D40186J | | | 3 | GD01716 | DC.. | F | | 001-099 |
| 0079 | 22 | | GK | | 5-0 | 38-14-11 | D40186J | | | 3 | TB0178Y | C027 | BJ | | 115-199 |
| 0080 | 20 | | GK | | 5-0 | 38-14-11 | D40186J | | | 4 | TB0178Y | C027 | BJ | | 115-199 |
| 0081 | 22 | | GK | | 6-0 | 38-14-11 | D41302J | | | 17 | GD01716 | DC.. | F | | 001-099 |
| 0081 | 22 | | GK | | 5-0 | 38-14-11 | D41302J | | | 17 | TB0178Y | C027 | BJ | | 115-199 |
| 0082 | 20 | | GK | | 3-0 | 38-14-11 | GD01716 | DC.. | F | | TB0178Y | C027 | BJ | | 115-199 |
| 0084 | 22 | | GK | | 7-0 | 30-21-11 | D41858J | | | 29 | TB0179A | C016 | 2 | | ALL |
| 0085 | 24 | | GK | | 5-0 | 30-31-11 | D41030J | | | 4 | TB0171Y | C004 | BJ | | 115-199 |
| 0086 | 24 | | GK | | 5-0 | 30-31-12 | TB0178Y | A009 | BJ | | D41032J | 32 | | | 115-199 |
| 0087 | 22 | | GK | | 6-0 | 29-22-11 | D40570J | | | 19 | TB0178Y | A010 | BJ | | 001-099 |
| 0087 | 22 | | GK | | 5-0 | 29-22-11 | D40570J | | | 19 | TB0177Y | A006 | BJ | | 115-199 |
| 0088 | 22 | | GK | | 5-0 | 76-11-21 | D40718J | | | 25 | TB0178Z | 11 | BJ | | 001-099 |
| 0088 | 22 | | GK | | 4-0 | 76-11-21 | D40718J | | | 25 | TB0178Z | 21 | BJ | | 115-199 |
| 0089 | 22 | | GK | | 5-0 | 29-22-11 | D40570J | | | 10 | D40738J | 6 | | | 115-199 |
| 0090 | 24 | | GK | | 4-0 | 38-32-21 | D40978J | | | 3 | SM00009 | | WI | | 001-099 |
| 0090 | 20 | | GK | | 5-0 | 38-32-21 | D40978J | | | 3 | TB0178Y | A020 | BJ | | 115-199 |
| 0091 | 24 | | GK | | 4-0 | 38-32-21 | D40496J | | | 2 | SM00009 | | WI | | 001-099 |
| 0091 | 20 | | GK | | 5-0 | 38-32-21 | D40496J | | | 2 | TB0178Y | A020 | BJ | | 115-199 |
| 0092 | 24 | | GK | | 4-0 | 38-32-21 | D41302J | | | 19 | SM00009 | | WI | | 001-099 |
| 0092 | 20 | | GK | | 5-0 | 38-32-21 | D41302J | | | 19 | TB0178Y | A020 | BJ | | 115-199 |
| 0096 | 18 | | GK | | 5-0 | 33-31-41 | D40760J | | | 2 | D41408J | 34 | | | 115-199 |
| 0097 | 20 | | GK | | 5-0 | 33-31-41 | D40760J | | | 1 | D40718J | 47 | | | 115-199 |
| 0098 | 22 | | GK | | 7-0 | 30-32-11 | D40912J | | | 21 | D03212 | A1 | | * | 001-099 |
| 0098 | 22 | | GK | | 5-0 | 30-32-11 | D40912J | | | 21 | TB0178Z | 22 | BJ | | 115-199 |
| 0099 | 22 | | GK | | 5-0 | 30-32-11 | TB0178Z | | | 25 | D41487J | 20 | | | 115-199 |
| 0100 | 24 | | GK | | 5-0 | 24-34-11 | D41748J | | | 26 | D41122J | 15 | | | 001-099 |
| 0100 | 22 | | GK | | 5-0 | 24-34-11 | D41748J | | | 26 | D41122J | 14 | | | 115-199 |
| 0101 | 24 | | GK | | 6-0 | 31-51-42 | D40570J | | | 14 | D41739J | 33 | | | 001-099 |
| 0101 | 24 | | GK | | 5-0 | 31-51-42 | D40570J | | | 14 | D41739J | 33 | | | 115-199 |
| 0102 | 20 | | GK | | 5-0 | 33-41-11 | D40594J | | | 4 | D41728J | 11 | | | 001-099 |
| 0102 | 20 | | GK | | 4-0 | 33-41-11 | D40594J | | | 4 | D41728J | 11 | | | 115-199 |
| 0103 | 22 | | GK | | 5-0 | 30-11-11 | D40570J | | | 51 | D42010J | 33 | | | 001-099 |
| 0103 | 22 | | GK | | 6-0 | 30-11-11 | D40570J | | | 51 | D42010J | 33 | | | 115-199 |
| 0104 | 22 | | GK | | 5-0 | 30-11-11 | D40570J | | | 52 | D42010J | 32 | | | 001-099 |
| 0104 | 22 | | GK | | 6-0 | 30-11-11 | D40570J | | | 52 | D42010J | 32 | | | 115-199 |
| 0105 | 22 | | GK | | 7-0 | 30-11-11 | D40570J | | | 50 | TB0178Y | A004 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 4

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0105 | 22 | | GK | | 5-0 | 30-11-11 | D40570J | | 50 | | TB0178Y | A004 | BJ | | 115-199 |
| 0109 | 20 | | GK | | 5-0 | 30-33-11 | D41122J | | 3 | | D41909J | 30 | | | 001-099 |
| 0109 | 20 | | GK | | 4-0 | 30-33-11 | D41122J | | 3 | | D41909J | 30 | | | 115-199 |
| 0110 | 22 | | GK | | 6-0 | 29-21-32 | D41852J | | 30 | | D41616J | 30 | | | ALL |
| 0111 | 22 | | GK | | 6-0 | 29-21-32 | D41852J | | 31 | | D41616J | 31 | | | ALL |
| 0112 | 20 | | GK | | 5-0 | 33-42-12 | D41408J | | 14 | | D41728J | 6 | | | 001-099 |
| 0112 | 20 | | GK | | 4-0 | 33-42-12 | D41408J | | 14 | | D41728J | 6 | | | 115-199 |
| 0113 | 20 | | GK | | 5-0 | 33-42-12 | D41408J | | 16 | | D41728J | 7 | | | 001-099 |
| 0113 | 20 | | GK | | 4-0 | 33-42-12 | D41408J | | 16 | | D41728J | 7 | | | 115-199 |
| 0114 | 20 | | GK | | 3-0 | 33-42-12 | D41408J | | 17 | | D40490J | 6 | | | 115-199 |
| 0115 | 20 | | GK | | 5-0 | 33-42-21 | D41408J | | 21 | | D40490J | 1 | | | 001-099 |
| 0115 | 20 | | GK | | 3-0 | 33-42-21 | D41408J | | 35 | | D40490J | 1 | | | 115-199 |
| 0117 | 20 | | GK | | 5-0 | 33-43-12 | D41852J | | 6 | | D41728J | 8 | | | 001-099 |
| 0117 | 20 | | GK | | 4-0 | 33-43-12 | D41852J | | 6 | | D41728J | 8 | | | 115-199 |
| 0118 | 24 | | GK | | 5-0 | SPARE | D41030J | | 40 | | D41994J | CAP | Y | | 003 |
| 0118 | 24 | | GK | | 5-0 | SPARE | D41030J | | 40 | | D41994J | 31 | | | 004-099 |
| 0119 | 22 | | GK | | 5-0 | 33-31-11 | D40978J | | 4 | | D41994J | 1 | | | 001-099 |
| 0119 | 22 | | GK | | 6-0 | 33-31-11 | D40978J | | 4 | | D41994J | 32 | | | 115-199 |
| 0120 | 24 | | GK | | 4-0 | 24-41-12 | D40978J | | 2 | | K00102 | 13 | C | | 115-199 |
| 0121 | 24 | | GK | | 4-0 | 24-41-12 | D40978J | | 1 | | K00102 | 12 | C | | 115-199 |
| 0125 | 22 | | GK | | 8-0 | 27-62-11 | D40594J | | 2 | | TB0173A | C011 | 2 | | 001-099 |
| 0125 | 20 | | GK | | 5-0 | 27-62-11 | D40594J | | 2 | | TB0178Y | C023 | BJ | | 115-199 |
| 0126 | 20 | | GK | | 6-0 | 27-62-11 | D41616J | | 9 | | TB0173A | C011 | 2 | * | 001-099 |
| 0126 | 20 | | GK | | 6-0 | 27-62-11 | D41616J | | 9 | | TB0178Y | C023 | BJ | | 115-199 |
| 0127 | 22 | | GK | | 6-0 | 27-62-11 | D41032J | | 7 | | TB0173A | C011 | 2 | * | 001-099 |
| 0127 | 20 | | GK | | 6-0 | 27-62-11 | D41032J | | 7 | | TB0178Y | C023 | BJ | | 115-199 |
| 0128 | 22 | | GK | | 6-0 | 27-62-11 | D41032J | | 8 | | D41766J | 6 | | | 001-099 |
| 0128 | 20 | | GK | | 6-0 | 27-62-11 | D41032J | | 8 | | D41766J | 6 | | | 115-199 |
| 0129 | 20 | | GK | | 6-0 | 27-62-11 | D41616J | | 33 | | TB0173Y | A002 | BJ | | 001-099 |
| 0129 | 20 | | GK | | 5-0 | 27-62-11 | D41616J | | 33 | | TB0178Y | A024 | BJ | | 115-199 |
| 0130 | 20 | | GK | | 6-0 | 27-62-11 | D41032J | | 52 | | TB0173Y | A019 | BJ | | 001-099 |
| 0130 | 20 | | GK | | 6-1 | 27-62-11 | D41030J | | 14 | | TB0173Y | A019 | BJ | | 115-199 |
| 0131 | 24 | | GK | | 9-0 | 35-21-11 | D02184 | | 1 | | D02180 | X2 | | | 001-099 |
| 0131 | 24 | | GK | | 11-0 | 35-21-11 | D02184 | | 1 | | D02180 | X2 | | | 115-199 |
| 0132 | 22 | | GK | | 7-0 | 35-21-11 | D02184 | | 2 | | GD01721 | DC.. | F | | ALL |
| 0135 | 24 | | GK | | 7-0 | 21-51-22 | D41856J | | 9 | | D03006 | X1 | | * | 001-099 |
| 0135 | 24 | | GK | | 4-0 | 21-51-22 | D41856J | | 9 | | D40064J | 57 | | | 115-199 |
| 0136 | 20 | | GK | | 6-0 | 21-45-11 | D41856J | | 7 | | TB0177Y | C005 | BJ | | 001-099 |
| 0136 | 20 | | GK | | 4-0 | 21-45-11 | D41856J | | 7 | | TB0178Y | C004 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 5

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 0140 | 22 | | GK | | 6-0 | 30-21-11 | D41858J | | 3 | | | TB0178Y | C010 | BJ | | 001-099 |
| 0140 | 22 | | GK | | 5-0 | 30-21-11 | D41858J | | 3 | | | TB0178Y | A027 | BJ | | 115-199 |
| 0141 | 22 | | GK | | 5-0 | 77-12-42 | D40738J | | 5 | | | D41994J | 4 | | | 001-099 |
| 0141 | 22 | | GK | | 4-0 | 77-12-42 | D40738J | | 5 | | | D41994J | 4 | | | 115-199 |
| 0145 | 24 | | GK | | 3-0 | 36-11-22 | D41860J | | 2 | | | SM00011 | | WI | | 001-099 |
| 0145 | 24 | | GK | | 5-0 | 36-11-22 | D41860J | | 2 | | | TB0178Y | C028 | BJ | | 115-199 |
| 0146 | 24 | | GK | | 5-0 | 36-11-22 | D40064J | | 7 | | | SM00011 | | WI | | 001-099 |
| 0146 | 24 | | GK | | 5-0 | 36-11-22 | D40064J | | 7 | | | TB0178Y | C028 | BJ | | 115-199 |
| 0147 | 24 | | GK | | 3-0 | 36-11-22 | D41860J | | 3 | | | SM00011 | | WI | | 001-099 |
| 0147 | 24 | | GK | | 5-0 | 36-11-22 | D41860J | | 3 | | | TB0178Y | C028 | BJ | | 115-199 |
| 0157 | 22 | | GK | | 4-0 | 29-31-11 | D41854J | | 29 | | | D41732J | 7 | | | ALL |
| 0158 | 22 | | GK | | 6-0 | 52-35-11 | D40186J | | 21 | | | D41546J | 41 | | | 115-199 |
| 0159 | 22 | | GK | | 6-0 | 52-35-11 | D40186J | | 20 | | | D41546J | 35 | | | 115-199 |
| 0160 | 22 | | GK | | 6-0 | 52-35-11 | D40186J | | 22 | | | D41546J | 36 | | | 115-199 |
| 0161 | 24 | | GK | | 9-0 | 23-12-21 | D00612 | | 1 | | | D41909J | 21 | | | ALL |
| 0162 | 24 | | GK | | 3-0 | 23-12-21 | D00612 | | 13 | | | GD01702 | DC.. | 2 | | 001-099 |
| 0162 | 24 | | GK | | 4-0 | 23-12-21 | D00612 | | 13 | | | GD01703 | DC.. | 2 | | 115-199 |
| 0165 | 18 | | GK | | 6-0 | 28-22-11 | D41408J | | 36 | | | TB0178G | 19 | 2 | | 001-099 |
| 0165 | 18 | | GK | | 5-0 | 28-22-11 | D41408J | | 36 | | | TB0178G | 31 | 2 | | 115-199 |
| 0166 | 20 | | GK | | 5-0 | 21-51-22 | D40064J | | 3 | | | D40718J | 26 | | | 001-099 |
| 0166 | 24 | | GK | | 4-0 | 21-51-22 | D40064J | | 3 | | | D40718J | 26 | | | 115-199 |
| 0167 | 22 | | GK | | 4-0 | 33-22-11 | D40718J | | 52 | | | TB0178Z | 18 | BJ | | 115-199 |
| 0168 | 24 | | GK | | 6-0 | 29-35-11 | D40570J | | 7 | | | TB0178A | A015 | 2 | | 001-099 |
| 0168 | 24 | | GK | | 7-0 | 29-35-11 | D40570J | | 7 | | | TB0174C | A022 | 2 | | 115-199 |
| 0169 | 24 | | GK | | 6-0 | 29-35-11 | D41032J | | 37 | | | TB0178A | A016 | 2 | | 001-099 |
| 0169 | 24 | | GK | | 7-0 | 29-35-11 | D41032J | | 37 | | | TB0174C | A023 | 2 | | 115-199 |
| 0170 | 24 | | GK | | 5-0 | 29-35-11 | D42062J | | 12 | | | TB0178A | C017 | 2 | | 001-099 |
| 0170 | 24 | | GK | | 7-0 | 29-35-11 | D42008J | | 15 | | | TB0174C | C024 | 2 | | 115-199 |
| 0171 | 24 | | GK | | 5-0 | 29-35-11 | D41732J | | 8 | | | TB0178A | C015 | 2 | | 001-099 |
| 0171 | 24 | | GK | | 7-0 | 29-35-11 | D41732J | | 8 | | | TB0174C | C022 | 2 | | 115-199 |
| 0172 | 24 | | GK | | 6-0 | 29-35-11 | D41637J | | 9 | | | TB0178A | C016 | 2 | | 001-099 |
| 0172 | 24 | | GK | | 7-0 | 29-35-11 | D41637J | | 9 | | | TB0174C | C023 | 2 | | 115-199 |
| 0173 | 24 | | GK | | 9-0 | 36-22-11 | TB0179A | C001 | 2 | | | D42176J | 7 | | | 001-099 |
| 0174 | 22 | | GK | | 5-0 | 77-11-11 | D40718J | | 30 | | | D41998J | 7 | | | 001-099 |
| 0174 | 22 | | GK | | 5-0 | 77-11-11 | D41998J | | 7 | | | D40718J | 30 | | | 115-199 |
| 0175 | 24 | | GK | | 5-0 | 24-27-41 | D40978J | | 6 | | | D41684J | 9 | | | 001-099 |
| 0175 | 24 | | GK | | 4-0 | 24-27-41 | D40978J | | 6 | | | D41684J | 9 | | | 115-199 |
| 0176 | 20 | | GK | | 5-0 | 29-21-31 | D41034J | | 11 | | | D41994J | 20 | | | 001-099 |
| 0176 | 20 | | GK | | 4-0 | 29-21-31 | D41034J | | 11 | | | D41994J | 20 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 6

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0183 | 22 | | GK | | 8-0 | 32-42-11 | | D04268 | | 3 | | D41860J | | 6 | | 001-099 |
| 0183 | 22 | | GK | | 9-0 | 32-42-11 | | D04268 | | 3 | | D41860J | | 13 | | 115-199 |
| 0185 | 24 | | GK | | 6-0 | 24-28-11 | | D40978J | | 8 | | D41739J | | 22 | | 001-099 |
| 0185 | 24 | | GK | | 5-0 | 24-28-11 | | D40978J | | 8 | | D41739J | | 22 | | 115-199 |
| 0186 | 24 | | GK | | 6-0 | 24-28-11 | | D40978J | | 7 | | D41739J | | 30 | | 001-099 |
| 0186 | 24 | | GK | | 5-0 | 24-28-11 | | D40978J | | 7 | | D41739J | | 30 | | 115-199 |
| 0188 | 20 | | GK | | 7-0 | 33-43-11 | | D40594J | | 52 | | D41856J | | 32 | | 001-099 |
| 0188 | 20 | | GK | | 5-0 | 33-43-11 | | D40594J | | 52 | | D41856J | | 32 | | 115-199 |
| 0189 | 20 | | GK | | 7-0 | 33-41-11 | | D40594J | | 3 | | D41856J | | 54 | | 001-099 |
| 0189 | 20 | | GK | | 5-0 | 33-41-11 | | D40594J | | 3 | | D41856J | | 54 | | 115-199 |
| 0190 | 22 | | GK | | 7-0 | 32-42-11 | | D41487J | | 32 | | D04268 | | 7 | | 001-099 |
| 0190 | 22 | | GK | | 6-0 | 32-42-11 | | D41487J | | 32 | | D04268 | | 7 | | 115-199 |
| 0191 | 22 | | GK | | 5-0 | 32-42-11 | | D40594J | | 10 | | D41860J | | 7 | | 001-099 |
| 0192 | 20 | | GK | | 2-0 | 24-51-24 | | K10298 | X2 | C | | K00120 | X2 | C | * | ALL |
| 0193 | 20 | | GK | | 2-0 | 24-51-24 | | K10298 | X1 | C | | K00120 | X1 | C | * | ALL |
| 0194 | 20 | | GK | | 2-0 | 24-51-24 | | K10298 | 13 | C | | K00120 | 14 | C | | ALL |
| 0196 | 20 | | GK | | 7-0 | 80-11-21 | | D41994J | 17 | | | D42008J | 4 | | | 001-099 |
| 0230 | 22 | | GK | | 7-0 | 29-22-11 | | D41034J | 13 | | | TB0173A | A010 | 2 | | 001-099 |
| 0230 | 22 | | GK | | 9-0 | 29-22-11 | | D40570J | 24 | | | TB0173C | A010 | 2 | | 115-199 |
| 0231 | 22 | | GK | | 4-0 | 29-22-11 | | D05194 | 2 | | | TB0173Y | C014 | BJ | | 001-099 |
| 0231 | 22 | | GK | | 9-0 | 29-22-11 | | D40570J | 2 | | | D05194 | 2 | | | 115-199 |
| 0232 | 22 | | GK | | 6-0 | 29-22-11 | | D41994J | 29 | | | TB0173Y | C014 | BJ | | 001-099 |
| 0233 | 22 | | GK | | 7-0 | 29-22-11 | | D41034J | 14 | | | TB0173Y | C014 | BJ | | 001-099 |
| 0234 | 22 | | GK | | 7-0 | 32-09-12 | | D00624 | 8 | | | D41616J | 2 | | | 001-099 |
| 0234 | 22 | | GK | | 8-0 | 32-09-12 | | D00624 | 8 | | | D41616J | 2 | | | 115-199 |
| 0236 | 22 | | GK | | 3-0 | 32-09-12 | | D00624 | 7 | | | GD01701 | DC.. | 2 | | 001-099 |
| 0236 | 22 | | GK | | 4-0 | 32-09-12 | | D00624 | 7 | | | GD01701 | DC.. | 2 | | 115-199 |
| 0253 | 24 | | GK | | 7-0 | 21-25-11 | | D41030J | 9 | | | K00416 | X2 | C | | 001-099 |
| 0253 | 24 | | GK | | 6-0 | 21-25-11 | | D41030J | 9 | | | K00416 | X2 | C | | 115-199 |
| 0254 | 24 | | GK | | 7-0 | 21-58-12 | | D41032J | 11 | | | D04246 | 8 | | | 001-099 |
| 0254 | 24 | | GK | | 10-0 | 21-58-12 | | D41032J | 11 | | | D04246 | 8 | | | 115-199 |
| 0259 | 24 | | GK | | 1-0 | 21-58-12 | | D04246 | 6 | | | D04316 | 8 | | | 001-099 |
| 0259 | 24 | | GK | | 2-0 | 21-58-12 | | D04246 | 6 | | | D04316 | 8 | | | 115-199 |
| 0264 | 24 | | GK | | 6-0 | 73-21-22 | | D07008 | X1 | | | D42010J | 30 | | | 001-099 |
| 0264 | 24 | | GK | | 7-0 | 73-21-22 | | D07008 | X1 | | | D42010J | 30 | | | 115-199 |
| 0266 | 24 | | GK | | 6-0 | 73-21-22 | | D07008 | X2 | | | GD01708 | DC.. | 2 | | 001-099 |
| 0266 | 24 | | GK | | 5-0 | 73-21-22 | | D07008 | X2 | | | GD01708 | DC.. | 2 | | 115-199 |
| 0267 | 20 | | GK | | 6-0 | 73-21-22 | | D07008 | A2 | | * | D42010J | 29 | | | 001-099 |
| 0267 | 20 | | GK | | 7-0 | 73-21-22 | | D07008 | A2 | | * | D42010J | 29 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 7

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | |
| 0268 | 20 | GK | | | 6-0 | 73-21-22 | D07008 | A3 | | | GD01708 | DC.. | 2 | | 001-099 |
| 0268 | 20 | GK | | | 5-0 | 73-21-22 | D07008 | A3 | | | GD01708 | DC.. | 2 | | 115-199 |
| 0269 | 24 | GK | | | 6-0 | 73-21-22 | D07008 | C1 | * | | D07006 | X1 | | * | 001-099 |
| 0269 | 24 | GK | | | 5-0 | 73-21-22 | D07008 | C1 | * | | D07006 | X1 | | * | 115-199 |
| 0270 | 24 | GK | | | 3-0 | 73-21-22 | D07006 | X2 | | | GD01708 | DC.. | 2 | | 001-099 |
| 0270 | 24 | GK | | | 4-0 | 73-21-22 | D07006 | X2 | | | GD01708 | DC.. | 2 | | 115-199 |
| 0271 | 20 | GK | | | 6-0 | 73-21-22 | D07008 | A2 | * | | D07006 | A1 | | | 001-099 |
| 0271 | 20 | GK | | | 5-0 | 73-21-22 | D07008 | A2 | * | | D07006 | A1 | | | 115-199 |
| 0272 | 20 | GK | | | 3-0 | 73-21-22 | D07006 | A2 | | | GD01708 | DC.. | 2 | | 001-099 |
| 0272 | 20 | GK | | | 4-0 | 73-21-22 | D07006 | A2 | | | GD01708 | DC.. | 2 | | 115-199 |
| 0273 | 24 | GK | | | 6-0 | 73-21-22 | D07006 | X1 | * | | D42010J | 27 | | | 001-099 |
| 0273 | 24 | GK | | | 7-0 | 73-21-22 | D07006 | X1 | * | | D42010J | 27 | | | 115-199 |
| 0276 | 24 | GK | | | 4-0 | 27-32-21 | D00624 | 3 | | | TB0171Y | C002 | BJ | | 001-099 |
| 0276 | 24 | GK | | | 4-0 | 27-32-21 | D00624 | 3 | | | TB0170Y | A010 | BJ | | 115-199 |
| 0277 | 24 | GK | | | 7-0 | 27-32-21 | D41487J | 6 | | | TB0171Y | C002 | BJ | | 001-099 |
| 0277 | 24 | GK | | | 6-0 | 27-32-21 | D41487J | 6 | | | TB0170Y | A010 | BJ | | 115-199 |
| 0278 | 24 | GK | | | 4-0 | 27-32-21 | D00624 | 5 | | | GD01703 | DC.. | 2 | | ALL |
| 0279 | 20 | GK | | | 8-0 | 74-31-21 | D07026 | X2 | | | D42008J | 20 | | | 001-099 |
| 0279 | 20 | GK | | | 9-0 | 74-31-21 | D07026 | X2 | | | D42008J | 20 | | | 115-199 |
| 0282 | 20 | GK | | | 6-0 | 74-31-21 | D07026 | X1 | | | TB0178Y | C009 | BJ | | 001-099 |
| 0282 | 20 | GK | | | 4-0 | 74-31-21 | D07026 | X1 | | | TB0174Z | 11 | BJ | | 115-199 |
| 0283 | 20 | GK | | | 8-0 | 74-31-21 | D07026 | A1 | | | D42008J | 21 | | | 001-099 |
| 0283 | 20 | GK | | | 4-0 | 74-31-21 | D07026 | A1 | | | TB0174Y | A015 | BJ | | 115-199 |
| 0284 | 20 | GK | | | 8-0 | 74-31-21 | D07026 | A2 | | | D42008J | 16 | | | 001-099 |
| 0284 | 20 | GK | | | 9-0 | 74-31-21 | D07026 | A2 | | | D42008J | 16 | | | 115-199 |
| 0286 | 20 | GK | | | 7-0 | 74-31-21 | D07026 | B1 | | | D41994J | 33 | | | 001-099 |
| 0286 | 20 | GK | | | 4-0 | 74-31-21 | D07026 | B1 | | | TB0174Y | C015 | BJ | | 115-199 |
| 0287 | 20 | GK | | | 7-0 | 74-31-21 | D07026 | B2 | | | D41994J | 32 | | | 001-099 |
| 0287 | 20 | GK | | | 10-0 | 74-31-21 | D07026 | B2 | | | D41994J | 31 | | | 115-199 |
| 0288 | 20 | GK | | | 4-0 | 74-31-21 | D02470 | A3 | | | TB0174Y | A015 | BJ | | 115-199 |
| 0289 | 20 | GK | | | 4-0 | 74-31-21 | D02472 | A3 | | | TB0174Y | C015 | BJ | | 115-199 |
| 0293 | 20 | GK | | | 6-0 | 36-11-21 | D07038 | B3 | | | D41856J | 33 | | | 001-099 |
| 0293 | 20 | GK | | | 8-0 | 36-11-21 | D07038 | B3 | | | D41856J | 33 | | | 115-199 |
| 0294 | 20 | GK | | | 3-0 | 36-11-21 | D07038 | X2 | | | GD01708 | DC.. | 2 | | 001-099 |
| 0294 | 20 | GK | | | 11-0 | 36-11-21 | D07038 | X2 | | | GD01708 | DC.. | 2 | | 115-199 |
| 0295 | 20 | GK | | | 7-0 | 36-11-21 | D07038 | X1 | | | D41032J | 9 | | | 001-099 |
| 0295 | 20 | GK | | | 8-0 | 36-11-21 | D07038 | X1 | | | D41032J | 9 | | | 115-199 |
| 0296 | 20 | GK | | | 4-0 | 36-11-21 | D07038 | C1 | * | | D04008 | 7 | | | 001-099 |
| 0296 | 20 | GK | | | 8-0 | 36-11-21 | D07038 | C1 | | | TB0178Y | A003 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 8

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 0297 | 20 | | GK | | 3-0 | 36-11-21 | D05194 | | 9 | | | D07038 | | B2 | | 001-099 | |
| 0297 | 20 | | GK | | 11-0 | 36-11-21 | D07038 | | B2 | | | D05194 | | 9 | | 115-199 | |
| 0299 | 22 | | GK | | 7-0 | 76-11-12 | D02216 | | 1 | | | D42010J | | 2 | | 001-099 | |
| 0302 | 18 | | GK | | 8-0 | 21-44-11 | K10084 | | C2 | D | | TB0177F | A007 | 2 | | 001-099 | |
| 0302 | 18 | | GK | | 9-0 | 21-44-11 | K10084 | | C2 | D | | TB0178F | A007 | 2 | | 115-199 | |
| 0303 | 18 | | GK | | 8-0 | 21-44-11 | K10084 | | B2 | D | | TB0177F | C007 | 2 | | 001-099 | |
| 0303 | 18 | | GK | | 9-0 | 21-44-11 | K10084 | | B2 | D | | TB0178F | C007 | 2 | | 115-199 | |
| 0304 | 18 | | GK | | 8-0 | 21-44-11 | K10084 | | A2 | D | | TB0177F | C002 | 2 | | 001-099 | |
| 0304 | 18 | | GK | | 9-0 | 21-44-11 | K10084 | | A2 | D | | TB0178F | A008 | 2 | | 115-199 | |
| 0305 | 18 | | GK | | 7-0 | 21-44-11 | K10084 | | C1 | D | | D40184J | 12 | | | 001-099 | |
| 0305 | 18 | | GK | | 9-0 | 21-44-11 | K10084 | | C1 | D | | D40184J | 12 | | | 115-199 | |
| 0306 | 18 | | GK | | 7-0 | 21-44-11 | K10084 | | B1 | D | | D40184J | 11 | | | 001-099 | |
| 0306 | 18 | | GK | | 9-0 | 21-44-11 | K10084 | | B1 | D | | D40184J | 11 | | | 115-199 | |
| 0307 | 18 | | GK | | 5-0 | 21-44-11 | K10084 | | A1 | D | | TB0172G | 20 | 2 | | 001-099 | |
| 0307 | 18 | | GK | | 4-0 | 21-44-11 | K10084 | | A1 | D | | TB0173F | A009 | 2 | | 115-199 | |
| 0308 | 24 | | GK | | 8-0 | 21-44-11 | K10084 | | X1 | C | | D40186J | 16 | | | 001-099 | |
| 0308 | 24 | | GK | | 9-0 | 21-44-11 | K10084 | | X1 | C | | D40186J | 16 | | | 115-199 | |
| 0309 | 24 | | GK | | 4-0 | 21-44-11 | K10084 | | X2 | C | | TB0173A | A009 | 2 | | 001-099 | |
| 0309 | 24 | | GK | | 5-0 | 21-44-11 | K10084 | | X2 | C | | TB0172A | A001 | 2 | | 115-199 | |
| 0310 | 24 | | GK | | 4-0 | 21-44-11 | D02604 | | A2 | | | TB0173A | A009 | 2 | | 001-099 | |
| 0310 | 24 | | GK | | 6-0 | 21-44-11 | D02604 | | A2 | | | TB0172A | A001 | 2 | | 115-199 | |
| 0311 | 24 | | GK | | 2-0 | 21-44-11 | D02604 | | A1 | | | GD01710 | DC.. | 2 | | 001-099 | |
| 0311 | 24 | | GK | | 4-0 | 21-44-11 | D02604 | | A1 | | | GD01710 | DC.. | 2 | | 115-199 | |
| 0312 | 24 | | GK | | 4-0 | 21-44-11 | D02604 | | X1 | | | TB0173Y | A001 | BJ | | 001-099 | |
| 0312 | 24 | | GK | | 6-0 | 21-44-11 | D02604 | | X1 | | | TB0172Z | 5 | BJ | | 115-199 | |
| 0313 | 24 | | GK | | 4-0 | 21-44-11 | D02604 | | C1 | | | D07608 | A1 | | | 001-099 | |
| 0313 | 24 | | GK | | 5-0 | 21-44-11 | D02604 | | C1 | | | D02602 | A2 | | | 115-199 | |
| 0314 | 24 | | GK | | 2-0 | 21-44-11 | D02604 | | X2 | | | GD01710 | DC.. | 2 | | 001-099 | |
| 0314 | 24 | | GK | | 4-0 | 21-44-11 | D02604 | | X2 | | | GD01710 | DC.. | 2 | | 115-199 | |
| 0315 | 24 | | GK | | 8-0 | 21-44-11 | D40186J | | 17 | | | TB0173Y | A001 | BJ | | 001-099 | |
| 0315 | 20 | | GK | | 9-0 | 21-44-11 | D40186J | | 17 | | | TB0172Z | 5 | BJ | | 115-199 | |
| 0316 | 24 | | GK | | 6-0 | 21-44-11 | D41856J | | 43 | | | TB0173Y | A001 | BJ | | 001-099 | |
| 0316 | 24 | | GK | | 7-0 | 21-44-11 | D41856J | | 43 | | | TB0172Z | 5 | BJ | | 115-199 | |
| 0317 | 24 | | GK | | 2-0 | 21-44-11 | D02602 | | X1 | | | TB0172Z | 5 | BJ | | 115-199 | |
| 0318 | 24 | | GK | | 2-0 | 21-44-11 | D02602 | | A1 | | | TB0172Z | 5 | BJ | | 115-199 | |
| 0319 | 24 | | GK | | 6-0 | 21-44-11 | D02604 | | B2 | | | D41854J | 13 | | | 001-099 | |
| 0319 | 22 | | GK | | 6-0 | 21-44-11 | D02602 | | B2 | | | D41854J | 13 | | | 115-199 | |
| 0320 | 24 | | GK | | 1-0 | 21-44-11 | TB0172A | | C001 | 2 | | TB0172A | A002 | 2 | | 115-199 | |
| 0321 | 24 | | GK | | 8-0 | 21-44-11 | D40186J | | 18 | | | TB0173A | C009 | 2 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 9

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|------|--|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 0321 | 24 | | GK | 9-0 | 21-44-11 | D40186J | 18 | | | | | TB0172A | C002 | 2 | | 115-199 | |
| 0322 | 22 | | GK | 9-0 | 30-11-11 | D40570J | 39 | | | | | TB0172Y | C015 | BJ | | 115-199 | |
| 0323 | 24 | | GK | 3-0 | 21-44-11 | TB0173A | C009 | 2 | * | | | D02604 | B1 | | | 001-099 | |
| 0323 | 24 | | GK | 4-0 | 21-44-11 | TB0172A | C002 | 2 | | | | D02602 | B1 | | | 115-199 | |
| 0324 | 20 | | GK | 7-0 | 21-45-11 | D00620 | B2 | | | | | D41856J | 6 | | | 001-099 | |
| 0324 | 20 | | GK | 6-0 | 21-45-11 | D00620 | B2 | | | | | D41856J | 6 | | | 115-199 | |
| 0325 | 20 | | GK | 9-0 | 21-45-11 | D00620 | B1 | | | | | TB0177Y | C005 | BJ | | 001-099 | |
| 0325 | 20 | | GK | 9-0 | 21-45-11 | D00620 | B1 | | | | | TB0178Y | C004 | BJ | | 115-199 | |
| 0326 | 22 | | GK | 6-0 | 30-11-11 | D04610 | A3 | | * | | | D40570J | 39 | | | 001-099 | |
| 0326 | 22 | | GK | 4-0 | 30-11-11 | D04610 | A3 | | | | | TB0172Y | C015 | BJ | | 115-199 | |
| 0329 | 16 | | GK | 6-0 | 21-58-13 | K00344 | A1 | E | | | | D40912J | 41 | | | 001-099 | |
| 0329 | 16 | | GK | 6-0 | 21-58-13 | K00344 | A1 | E | | | | D40920J | 6 | | | 115-199 | |
| 0330 | 16 | | GK | 6-0 | 21-58-13 | K00344 | B1 | E | | | | D40912J | 40 | | | 001-099 | |
| 0330 | 16 | | GK | 6-0 | 21-58-13 | K00344 | B1 | E | | | | D40920J | 7 | | | 115-199 | |
| 0331 | 16 | | GK | 6-0 | 21-58-13 | K00344 | C1 | E | | | | D40912J | 27 | | | 001-099 | |
| 0331 | 16 | | GK | 6-0 | 21-58-13 | K00344 | C1 | E | | | | D40920J | 8 | | | 115-199 | |
| 0334 | 16 | | GK | 8-0 | 21-58-13 | K00344 | A2 | E | | | | D40050J | 8 | | | 001-099 | |
| 0334 | 16 | | GK | 7-0 | 21-58-13 | K00344 | A2 | E | | | | D40050J | 8 | | | 115-199 | |
| 0335 | 16 | | GK | 8-0 | 21-58-13 | K00344 | B2 | E | | | | D40050J | 9 | | | 001-099 | |
| 0335 | 16 | | GK | 7-0 | 21-58-13 | K00344 | B2 | E | | | | D40050J | 9 | | | 115-199 | |
| 0336 | 16 | | GK | 8-0 | 21-58-13 | K00344 | C2 | E | | | | D40050J | 10 | | | 001-099 | |
| 0336 | 16 | | GK | 7-0 | 21-58-13 | K00344 | C2 | E | | | | D40050J | 10 | | | 115-199 | |
| 0347 | 24 | | GK | 6-0 | 21-58-13 | D41860J | 1 | | | | | K00344 | 14 | C | | ALL | |
| 0349 | 24 | | GK | 6-0 | 23-31-13 | D02172 | 11 | | | | | D41739J | 1 | | | 001-099 | |
| 0349 | 24 | | GK | 5-0 | 23-31-13 | D02172 | 11 | | | | | D41739J | 1 | | | 115-199 | |
| 0350 | 24 | | GK | 2-0 | 23-31-13 | D02172 | 10 | | | | | GD01711 | DC.. | 2 | | 001-099 | |
| 0350 | 24 | | GK | 4-0 | 23-31-13 | D02172 | 10 | | | | | GD01711 | DC.. | 2 | | 115-199 | |
| 0351 | 24 | | GK | 8-0 | 24-51-71 | D41748J | 10 | | | | | D01610 | C2 | | | 001-099 | |
| 0351 | 24 | | GK | 9-0 | 24-51-71 | D41748J | 10 | | | | | D01610 | C2 | | | 115-199 | |
| 0352 | 24 | | GK | 7-0 | 24-51-71 | SM00002 | | WI | | | | D01610 | C1 | | | 001-099 | |
| 0352 | 24 | | GK | 2-0 | 24-51-71 | TB0172Y | A004 | BJ | | | | D01610 | C1 | | | 115-199 | |
| 0353 | 24 | | GK | 3-0 | 24-51-71 | SM00002 | | WI | | | | D41748J | 8 | | | 001-099 | |
| 0353 | 24 | | GK | 9-0 | 24-51-71 | TB0172Y | A004 | BJ | | | | D41748J | 8 | | | 115-199 | |
| 0354 | 24 | | GK | 3-0 | 24-51-71 | SM00002 | | WI | | | | D41748J | 1 | | | 001-099 | |
| 0354 | 24 | | GK | 9-0 | 24-51-71 | TB0172Y | A004 | BJ | | | | D41748J | 1 | | | 115-199 | |
| 0355 | 24 | | GK | 6-0 | 24-51-71 | D02084 | 5 | | | | | D41854J | 1 | | | ALL | |
| 0356 | 24 | | GK | 10-0 | 24-51-71 | D02084 | 2 | | | | | D00632 | 2 | | | 001-099 | |
| 0356 | 24 | | GK | 9-0 | 24-51-71 | D02084 | 2 | | | | | TB0178X | B005 | BJ | | 115-199 | |
| 0357 | 24 | | GK | 3-0 | 24-51-71 | D02084 | 7 | | | | | TB0173Y | C001 | BJ | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 10

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0357 | 24 | | GK | | 9-0 | 24-51-71 | D02084 | | 7 | | TB0178Y | C003 | BJ | | 115-199 |
| 0358 | 24 | | GK | | 2-0 | 24-51-71 | D02084 | | 3 | | GD01709 | DC.. | 2 | | 001-099 |
| 0358 | 24 | | GK | | 4-0 | 24-51-71 | D02084 | | 3 | | GD01709 | DC.. | 2 | | 115-199 |
| 0359 | 22 | | GK | | 3-0 | 30-11-11 | D04610 | | A3 | * | M10479 | A | C | | 001-099 |
| 0359 | 22 | | GK | | 3-0 | 30-11-11 | TB0172Y | | C015 | BJ | M10479 | A | C | | 115-199 |
| 0360 | 22 | | GK | | 3-0 | 30-11-11 | D04610 | | X1 | | M10479 | B | C | | 001-099 |
| 0360 | 22 | | GK | | 4-0 | 30-11-11 | D04610 | | X1 | | M10479 | B | C | | 115-199 |
| 0361 | 20 | | GK | | 3-0 | 27-62-11 | D03206 | | 4 | | TB0173Y | A002 | BJ | | 001-099 |
| 0361 | 20 | | GK | | 9-0 | 27-62-11 | D03206 | | 4 | | TB0178Y | A024 | BJ | | 115-199 |
| 0362 | 20 | | GK | | 6-0 | 27-62-11 | D03206 | | 5 | | D41616J | 34 | | | 001-099 |
| 0362 | 20 | | GK | | 4-0 | 27-62-11 | D03206 | | 5 | | D41616J | 34 | | | 115-199 |
| 0363 | 20 | | GK | | 3-0 | 27-62-11 | D03206 | | 3 | | TB0173Y | A003 | BJ | | ALL |
| 0364 | 20 | | GK | | 6-0 | 27-62-11 | D41030J | | 5 | | TB0173Y | A003 | BJ | | 001-099 |
| 0364 | 20 | | GK | | 5-0 | 27-62-11 | D41030J | | 5 | | TB0173Y | A003 | BJ | | 115-199 |
| 0365 | 20 | | GK | | 6-0 | 27-62-11 | D41030J | | 16 | | TB0173Y | A003 | BJ | | 001-099 |
| 0365 | 20 | | GK | | 5-0 | 27-62-11 | D41030J | | 16 | | TB0173Y | A003 | BJ | | 115-199 |
| 0366 | 20 | | GK | | 3-0 | 27-62-11 | TB0173B | | C012 | 2 | D03206 | 7 | | | 001-099 |
| 0366 | 20 | | GK | | 5-0 | 27-62-11 | TB0173B | | C014 | 2 | D03206 | 7 | | | 115-199 |
| 0367 | 22 | | GK | | 10-0 | 27-62-11 | TB0173Y | | A020 | BJ | D03206 | 2 | | | ALL |
| 0368 | 18 | | GK | | 9-0 | 33-24-11 | D41302J | | 15 | 18 | GD01711 | AC.. | 2 | | 115-199 |
| 0370 | 18 | | GK | | 9-0 | 33-24-11 | D40496J | | 30 | 18 | GD01711 | AC.. | 2 | | 115-199 |
| 0371 | 24 | | GK | | 2-0 | 33-24-11 | D02172 | | 4 | | GD01711 | DC.. | 2 | | 001-099 |
| 0371 | 22 | | GK | | 4-0 | 33-24-11 | D02172 | | 4 | | GD01711 | DC.. | 2 | | 115-199 |
| 0372 | 24 | | GK | | 8-0 | 33-24-11 | D02172 | | 5 | | D41408J | 6 | | | 001-099 |
| 0372 | 22 | | GK | | 9-0 | 33-24-11 | D02172 | | 5 | | D41408J | 6 | | | 115-199 |
| 0373 | 16 | | GK | | 6-0 | 35-21-11 | D40738J | | 18 | | TB0172G | 3 | 2 | | 001-099 |
| 0373 | 16 | | GK | | 8-0 | 35-21-11 | D40738J | | 18 | | TB0172G | 9 | 2 | | 115-199 |
| 0374 | 16 | | GK | | 3-0 | 35-21-11 | D02178 | | B2 | | TB0172G | 3 | 2 | | 001-099 |
| 0374 | 16 | | GK | | 2-0 | 35-21-11 | D02178 | | B2 | | TB0172G | 9 | 2 | | 115-199 |
| 0375 | 16 | | GK | | 3-0 | 35-21-11 | D02180 | | B2 | | TB0172G | 3 | 2 | | 001-099 |
| 0375 | 16 | | GK | | 2-0 | 35-21-11 | D02180 | | B2 | | TB0172G | 9 | 2 | | 115-199 |
| 0376 | 16 | | GK | | 6-0 | 35-21-11 | D40738J | | 16 | | TB0172G | 4 | 2 | | 001-099 |
| 0376 | 16 | | GK | | 8-0 | 35-21-11 | D40738J | | 16 | | TB0172G | 10 | 2 | | 115-199 |
| 0377 | 16 | | GK | | 3-0 | 35-21-11 | D02178 | | A2 | | TB0172G | 4 | 2 | | 001-099 |
| 0377 | 16 | | GK | | 2-0 | 35-21-11 | D02178 | | A2 | | TB0172G | 10 | 2 | | 115-199 |
| 0378 | 16 | | GK | | 3-0 | 35-21-11 | D02180 | | A2 | | TB0172G | 4 | 2 | | 001-099 |
| 0378 | 16 | | GK | | 2-0 | 35-21-11 | D02180 | | A2 | | TB0172G | 10 | 2 | | 115-199 |
| 0379 | 24 | | GK | | 6-0 | 35-21-11 | D40738J | | 2 | | D02178 | X1 | | | 001-099 |
| 0379 | 24 | | GK | | 8-0 | 35-21-11 | D40738J | | 2 | | D02178 | X1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 11

Jan 21/2005



WIRE LIST

91-21-11

Section W1270

Page 12

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0410 | 20 | | GK | | 6-0 | 28-25-11 | D41546J | | 38 | | K00188 | | C1 | D | 115-199 |
| 0411 | 22 | | GK | | 2-0 | 35-21-11 | D02172 | | 12 | | GD01711 | | DC.. | 2 | 001-099 |
| 0411 | 22 | | GK | | 4-0 | 35-21-11 | D02172 | | 12 | | GD01711 | | DC.. | 2 | 115-199 |
| 0412 | 22 | | GK | | 2-0 | 35-21-11 | D02172 | | 2 | | GD01711 | | DC.. | 2 | 001-099 |
| 0412 | 22 | | GK | | 4-0 | 35-21-11 | D02172 | | 2 | | GD01711 | | DC.. | 2 | 115-199 |
| 0430 | 24 | | GK | | 5-0 | 36-11-21 | D41856J | | 37 | | TB0178Y | | C019 | BJ | 115-199 |
| 0431 | 24 | | GK | | 5-0 | 36-11-21 | D41856J | | 38 | | TB0178Y | | C019 | BJ | 115-199 |
| 0432 | 24 | | GK | | 5-0 | 36-11-21 | D41856J | | 34 | | TB0178Y | | C019 | BJ | 115-199 |
| 0433 | 20 | | GK | | 2-0 | 36-11-21 | D04008 | | 3 | | GD01710 | | DC.. | 2 | ALL |
| 0434 | 24 | | GK | | 7-0 | 36-11-31 | D40738J | | 4 | | TB0173Y | | C004 | BJ | 001-099 |
| 0434 | 24 | | GK | | 8-0 | 36-11-31 | D40738J | | 4 | | TB0173Y | | C004 | BJ | 115-199 |
| 0437 | 24 | | GK | | 2-0 | 36-11-31 | D01602 | | 7 | | TB0173Y | | C004 | BJ | 001-099 |
| 0437 | 24 | | GK | | 3-0 | 36-11-31 | D01602 | | 7 | | TB0173Y | | C004 | BJ | 115-199 |
| 0438 | 24 | | GK | | 2-0 | 36-11-31 | D01600 | | 7 | | TB0173Y | | C004 | BJ | 001-099 |
| 0438 | 24 | | GK | | 4-0 | 36-11-31 | D01600 | | 7 | | TB0173Y | | C004 | BJ | 115-199 |
| 0439 | 24 | | GK | | 6-0 | 36-11-31 | D01600 | | 2 | | D41854J | | 5 | | 001-099 |
| 0439 | 24 | | GK | | 4-0 | 36-11-31 | D01600 | | 2 | | D41854J | | 5 | | 115-199 |
| 0440 | 24 | | GK | | 2-0 | 36-11-31 | D01600 | | 4 | | GD01710 | | DC.. | 2 | 001-099 |
| 0440 | 24 | | GK | | 4-0 | 36-11-31 | D01600 | | 4 | | GD01710 | | DC.. | 2 | 115-199 |
| 0441 | 24 | | GK | | 6-0 | 36-11-31 | D01600 | | 3 | | D41994J | | 23 | | 001-099 |
| 0441 | 24 | | GK | | 5-0 | 36-11-31 | D01600 | | 3 | | D41994J | | 23 | | 115-199 |
| 0442 | 24 | | GK | | 4-0 | 36-11-31 | D01602 | | 2 | | D41854J | | 4 | | ALL |
| 0443 | 24 | | GK | | 2-0 | 36-11-31 | D01602 | | 4 | | GD01710 | | DC.. | 2 | ALL |
| 0444 | 24 | | GK | | 2-0 | 36-11-31 | D01602 | | 1 | | GD01710 | | DC.. | 2 | ALL |
| 0445 | 24 | | GK | | 6-0 | 36-11-31 | D01602 | | 6 | | D41856J | | 2 | | 001-099 |
| 0445 | 24 | | GK | | 4-0 | 36-11-31 | D01602 | | 6 | | D41856J | | 2 | | 115-199 |
| 0446 | 24 | | GK | | 6-0 | 36-11-31 | D01602 | | 3 | | D41994J | | 24 | | 001-099 |
| 0446 | 24 | | GK | | 5-0 | 36-11-31 | D01602 | | 3 | | D41994J | | 24 | | 115-199 |
| 0447 | 24 | | GK | | 6-0 | 36-11-31 | D40570J | | 44 | | D41994J | | 22 | | 001-099 |
| 0447 | 24 | | GK | | 5-0 | 36-11-31 | D40570J | | 44 | | D41994J | | 22 | | 115-199 |
| 0448 | 24 | | GK | | 6-0 | 36-11-31 | D40570J | | 45 | | D41994J | | 21 | | 001-099 |
| 0448 | 24 | | GK | | 5-0 | 36-11-31 | D40570J | | 45 | | D41994J | | 21 | | 115-199 |
| 0449 | 20 | | GK | | 7-0 | 36-11-41 | D01610 | | A2 | | D40718J | | 35 | | 001-099 |
| 0449 | 20 | | GK | | 8-0 | 36-11-41 | D01610 | | A2 | | D40718J | | 38 | | 115-199 |
| 0450 | 24 | | GK | | 3-0 | 36-11-41 | TB0173Y | A005 | BJ | | D04006 | | 3 | | 001-099 |
| 0450 | 24 | | GK | | 10-0 | 36-11-41 | TB0177Y | A008 | BJ | | D04006 | | 3 | | 115-199 |
| 0451 | 24 | | GK | | 6-0 | 36-11-41 | D04008 | | 6 | | D41032J | | 31 | | 001-099 |
| 0451 | 24 | | GK | | 4-0 | 36-11-41 | D04008 | | 6 | | D41032J | | 31 | | 115-199 |
| 0452 | 24 | | GK | | 8-0 | 36-11-41 | D01610 | | B2 | | D40570J | | 13 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 13

Jan 21/2005



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|---------|--------|---|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 0452 | 24 | | GK | | 9-0 | 36-11-41 | | D01610 | | B2 | | D40570J | 13 | | | 115-199 | |
| 0453 | 24 | | GK | | 8-0 | 36-11-41 | | D01610 | | X2 | | D40570J | 23 | | | 001-099 | |
| 0453 | 24 | | GK | | 9-0 | 36-11-41 | | D01610 | | X2 | | D40570J | 9 | | | 115-199 | |
| 0454 | 20 | | GK | | 8-0 | 36-11-41 | | D01610 | | A3 | | D41684J | 5 | | | 001-099 | |
| 0454 | 20 | | GK | | 9-0 | 36-11-41 | | D01610 | | A3 | | D41684J | 5 | | | 115-199 | |
| 0455 | 20 | | GK | | 8-0 | 36-11-41 | | D01610 | | A1 | | D41684J | 4 | | | 001-099 | |
| 0455 | 20 | | GK | | 9-0 | 36-11-41 | | D01610 | | A1 | | D41684J | 4 | | | 115-199 | |
| 0456 | 24 | | GK | | 4-0 | 36-11-41 | | D01610 | | B3 | | D01612 | 2 | | | ALL | |
| 0457 | 24 | | GK | | 4-0 | 36-11-41 | | D01610 | | B1 | | D01614 | 5 | | | ALL | |
| 0458 | 24 | | GK | | 7-0 | 36-11-41 | | D04006 | | 6 | | D40570J | 1 | | | 001-099 | |
| 0458 | 24 | | GK | | 9-0 | 36-11-41 | | D04006 | | 6 | | D40570J | 1 | | | 115-199 | |
| 0459 | 24 | | GK | | 4-0 | 36-11-41 | | D04006 | | 8 | | D01610 | X1 | | | 001-099 | |
| 0459 | 24 | | GK | | 9-0 | 36-11-41 | | D04006 | | 8 | | D40570J | 12 | | | 115-199 | |
| 0460 | 24 | | GK | | 2-0 | 36-11-41 | | D01614 | | 3 | | GD01711 | DC.. | 2 | | ALL | |
| 0461 | 24 | | GK | | 3-0 | 36-11-41 | | D01614 | | 7 | | TB0173Z | 17 | BJ | | 001-099 | |
| 0461 | 24 | | GK | | 4-0 | 36-11-41 | | D01614 | | 7 | | TB0173Z | 1 | BJ | | 115-199 | |
| 0462 | 24 | | GK | | 8-0 | 36-11-41 | | D40570J | | 55 | | TB0173Z | 17 | BJ | | 001-099 | |
| 0462 | 24 | | GK | | 6-0 | 36-11-41 | | D01610 | | X1 | | TB0173Z | 1 | BJ | | 115-199 | |
| 0463 | 24 | | GK | | 3-0 | 36-11-41 | | D01614 | | 6 | | TB0173Z | 17 | BJ | | 001-099 | |
| 0463 | 24 | | GK | | 4-0 | 36-11-41 | | D01614 | | 6 | | TB0173Z | 1 | BJ | | 115-199 | |
| 0464 | 24 | | GK | | 3-0 | 36-11-41 | | D01612 | | 7 | | TB0173Z | 17 | BJ | | 001-099 | |
| 0464 | 24 | | GK | | 4-0 | 36-11-41 | | D01612 | | 7 | | TB0173Z | 1 | BJ | | 115-199 | |
| 0465 | 24 | | GK | | 7-0 | 36-11-41 | | D40718J | | 2 | | TB0173Z | 17 | BJ | | 001-099 | |
| 0465 | 24 | | GK | | 8-0 | 36-11-41 | | D40718J | | 2 | | TB0173Z | 1 | BJ | | 115-199 | |
| 0466 | 24 | | GK | | 2-0 | 36-11-41 | | D04006 | | 7 | | TB0173Z | 17 | BJ | | 001-099 | |
| 0466 | 24 | | GK | | 4-0 | 36-11-41 | | D04006 | | 7 | | TB0173Z | 1 | BJ | | 115-199 | |
| 0467 | 24 | | GK | | 3-0 | 36-11-41 | | D40570J | | 11 | | D41684J | 1 | | | 115-199 | |
| 0468 | 24 | | GK | | 8-0 | 36-11-41 | | D01614 | | 12 | | D41684J | 3 | | | 001-099 | |
| 0468 | 24 | | GK | | 9-0 | 36-11-41 | | D01614 | | 12 | | D41684J | 3 | | | 115-199 | |
| 0469 | 24 | | GK | | 8-0 | 36-11-41 | | D01614 | | 8 | | D41684J | 2 | | | 001-099 | |
| 0469 | 24 | | GK | | 9-0 | 36-11-41 | | D01614 | | 8 | | D41684J | 2 | | | 115-199 | |
| 0470 | 24 | | GK | | 2-0 | 36-11-41 | | D01612 | | 4 | | GD01711 | DC.. | 2 | | ALL | |
| 0471 | 24 | | GK | | 8-0 | 36-11-41 | | D01612 | | 3 | | D41684J | 6 | | | 001-099 | |
| 0471 | 20 | | GK | | 9-0 | 36-11-41 | | D01612 | | 3 | | D41684J | 6 | | | 115-199 | |
| 0472 | 20 | | GK | | 7-0 | 28-22-11 | | D42176J | | 3 | | K00188 | X1 | C | * | 001-099 | |
| 0472 | 20 | | GK | | 9-0 | 28-22-11 | | D42176J | | 3 | | K00188 | X1 | C | * | 115-199 | |
| 0475 | 18 | | GK | | 2-0 | 28-22-11 | | GD01710 | AC.. | 2 | | K10012 | X2 | C | | ALL | |
| 0477 | 20 | | GK | | 7-0 | 28-22-11 | | K00189 | | C1 | D | * | D42176J | 1 | | 001-099 | |
| 0477 | 20 | | GK | | 9-0 | 28-22-11 | | K00189 | | C1 | D | * | D42176J | 1 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0478 | 20 | | GK | | 7-0 | 28-22-11 | | D42176J | | 2 | | K00189 | X1 | C | | 001-099 |
| 0478 | 20 | | GK | | 9-0 | 28-22-11 | | D42176J | | 2 | | K00189 | X1 | C | | 115-199 |
| 0480 | 20 | | GK | | 6-0 | 28-22-11 | | D41856J | | 51 | | K00188 | C1 | D | * | 001-099 |
| 0480 | 20 | | GK | | 5-0 | 28-22-11 | | D41856J | | 51 | | K00188 | C1 | D | * | 115-199 |
| 0481 | 22 | | GK | | 3-0 | 30-32-11 | | D04244 | | B1 | | D04314 | B1 | | * | 001-099 |
| 0481 | 22 | | GK | | 5-0 | 30-32-11 | | D04244 | | B1 | | TB0178Z | 22 | BJ | | 115-199 |
| 0482 | 22 | | GK | | 3-0 | 30-32-11 | | D04244 | | B2 | | D04314 | B2 | | * | 001-099 |
| 0482 | 22 | | GK | | 5-0 | 30-32-11 | | D04244 | | B2 | | TB0178Z | 25 | BJ | | 115-199 |
| 0483 | 22 | | GK | | 10-0 | 30-32-11 | | D04314 | | B1 | * | D00634 | C3 | | * | 001-099 |
| 0483 | 22 | | GK | | 5-0 | 30-32-11 | | D04314 | | B1 | | TB0178Z | 22 | BJ | | 115-199 |
| 0484 | 22 | | GK | | 10-0 | 30-32-11 | | D04314 | | B2 | * | D03212 | A2 | | * | 001-099 |
| 0484 | 22 | | GK | | 5-0 | 30-32-11 | | D04314 | | B2 | | TB0178Z | 25 | BJ | | 115-199 |
| 0486 | 20 | | GK | | 7-0 | 28-22-11 | | D42176J | | 4 | | K00188 | X1 | C | * | 001-099 |
| 0486 | 20 | | GK | | 9-0 | 28-22-11 | | D42176J | | 4 | | K00188 | X1 | C | * | 115-199 |
| 0488 | 24 | | GK | | 10-0 | 30-31-12 | | D10750 | | A2 | | D02086 | B1 | | | 001-099 |
| 0488 | 24 | | GK | | 9-0 | 30-31-12 | | D10750 | | A2 | | TB0178X | A030 | BJ | | 115-199 |
| 0492 | 20 | | GK | | 9-0 | 36-11-21 | | D07038 | | C1 | * | D03056 | 4 | | | 001-099 |
| 0492 | 20 | | GK | | 9-0 | 36-11-21 | | D04008 | | 7 | | TB0178Y | A003 | BJ | | 115-199 |
| 0497 | 20 | | GK | | 8-0 | 25-31-21 | | D04494 | | C2 | | D40718J | 37 | | | 115-199 |
| 0498 | 20 | | GK | | 9-0 | 25-31-21 | | D04494 | | C3 | | D41748J | 7 | | | 115-199 |
| 0499 | 20 | | GK | | 7-0 | 25-31-33 | | D04494 | | B2 | | D41854J | 2 | | | 115-199 |
| 0500 | 20 | | GK | | 7-0 | 25-31-33 | | D04494 | | B3 | | D41854J | 12 | | | 115-199 |
| 0501 | 18 | | GK | | 6-0 | 38-15-11 | | D40912J | | 30 | | TB0178G | 14 | 2 | | 115-199 |
| 0502 | 18 | | GK | | 7-0 | 38-15-11 | | D00060 | | C2 | | D40912J | 30 | | | 001-099 |
| 0502 | 18 | | GK | | 9-0 | 38-15-11 | | D00060 | | C2 | | TB0178G | 14 | 2 | | 115-199 |
| 0503 | 18 | | GK | | 6-0 | 38-15-11 | | D00060 | | X1 | | SM00032 | | WI | | 001-099 |
| 0503 | 18 | | GK | | 9-0 | 38-15-11 | | D00060 | | X1 | | TB0178G | 14 | 2 | | 115-199 |
| 0504 | 18 | | GK | | 7-0 | 38-15-11 | | D00060 | | B2 | | D40912J | 29 | | | 001-099 |
| 0504 | 18 | | GK | | 6-0 | 38-15-11 | | D40912J | | 29 | | D00060 | B2 | | | 115-199 |
| 0505 | 18 | | GK | | 7-0 | 38-15-11 | | D00060 | | A2 | | D40912J | 28 | | | 001-099 |
| 0505 | 18 | | GK | | 6-0 | 38-15-11 | | D40912J | | 28 | | D00060 | A2 | | | 115-199 |
| 0506 | 18 | | GK | | 8-0 | 38-15-11 | | D00060 | | X2 | | D40184J | 9 | | | 001-099 |
| 0506 | 18 | | GK | | 9-0 | 38-15-11 | | D40184J | | 9 | | D00060 | X2 | | | 115-199 |
| 0507 | 18 | | GK | | 8-0 | 38-15-11 | | D00060 | | C1 | | D40184J | 8 | | | 001-099 |
| 0507 | 18 | | GK | | 9-0 | 38-15-11 | | D40184J | | 8 | | D00060 | C1 | | | 115-199 |
| 0508 | 18 | | GK | | 8-0 | 38-15-11 | | D00060 | | B1 | | D40184J | 7 | | | 001-099 |
| 0508 | 18 | | GK | | 9-0 | 38-15-11 | | D40184J | | 7 | | D00060 | B1 | | | 115-199 |
| 0509 | 18 | | GK | | 8-0 | 38-15-11 | | D00060 | | A1 | | D40184J | 6 | | | 001-099 |
| 0509 | 18 | | GK | | 9-0 | 38-15-11 | | D40184J | | 6 | | D00060 | A1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 15

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0544 | 20 | | GK | | 2-0 | 35-11-13 | D04112 | | X2 | | GD01709 | DC.. | 2 | | 115-199 |
| 0549 | 24 | | GK | | 8-0 | 36-11-41 | TB0173Y | | A005 | BJ | D04008 | | 8 | | 001-099 |
| 0549 | 24 | | GK | | 10-0 | 36-11-41 | TB0177Y | | A008 | BJ | D04008 | | 8 | | 115-199 |
| 0550 | 22 | | GK | | 3-0 | 77-12-42 | D05194 | | 12 | | GD01711 | DC.. | 2 | | 001-099 |
| 0550 | 22 | | GK | | 4-0 | 77-12-42 | D05194 | | 12 | | GD01708 | DC.. | 2 | | 115-199 |
| 0551 | 22 | | GK | | 3-0 | 77-12-42 | D05194 | | 6 | | TB0173Y | C005 | BJ | | 001-099 |
| 0551 | 22 | | GK | | 9-0 | 77-12-42 | D05194 | | 6 | | TB0178Y | C037 | BJ | | 115-199 |
| 0552 | 22 | | GK | | 6-0 | 77-12-42 | D42010J | | 20 | | TB0173Y | C005 | BJ | | 001-099 |
| 0552 | 22 | | GK | | 5-0 | 77-12-42 | D42010J | | 20 | | TB0178Y | C037 | BJ | | 115-199 |
| 0553 | 22 | | GK | | 6-0 | 29-22-11 | D41616J | | 38 | | TB0173A | C010 | 2 | | 001-099 |
| 0553 | 22 | | GK | | 5-0 | 29-22-11 | D41616J | | 38 | | TB0173C | C010 | 2 | | 115-199 |
| 0555 | 14 | | GA | | 6-0 | 21-25-11 | D40050J | | 1 | | K00416 | A2 | E | | ALL |
| 0556 | 14 | | GA | | 6-0 | 21-25-11 | D40050J | | 2 | | K00416 | B2 | E | | ALL |
| 0557 | 14 | | GA | | 6-0 | 21-25-11 | D40050J | | 11 | | K00416 | C2 | E | | ALL |
| 0561 | 24 | | GK | | 6-0 | 21-25-11 | K00416 | | X1 | C | D41030J | | 41 | | ALL |
| 0573 | 22 | | GK | | 3-0 | 29-22-11 | D05194 | | 13 | | TB0173Y | C003 | BJ | | 001-099 |
| 0573 | 22 | | GK | | 4-0 | 29-22-11 | D05194 | | 13 | | TB0173Y | C003 | BJ | | 115-199 |
| 0574 | 22 | | GK | | 3-0 | 29-22-11 | D05194 | | 1 | | TB0173A | A010 | 2 | | 001-099 |
| 0574 | 22 | | GK | | 4-0 | 29-22-11 | D05194 | | 1 | | TB0173C | A010 | 2 | | 115-199 |
| 0575 | 22 | | GK | | 6-0 | 29-22-11 | D41994J | | 27 | | TB0173Y | C003 | BJ | | 001-099 |
| 0575 | 22 | | GK | | 5-0 | 29-22-11 | D41994J | | 27 | | TB0173Y | C003 | BJ | | 115-199 |
| 0576 | 22 | | GK | | 6-0 | 29-22-11 | D41994J | | 28 | | TB0173Y | C003 | BJ | | 001-099 |
| 0576 | 22 | | GK | | 5-0 | 29-22-11 | D41994J | | 28 | | TB0173Y | C003 | BJ | | 115-199 |
| 0577 | 24 | | GK | | 3-0 | 36-11-41 | D01600 | | 8 | | TB0173Y | C006 | BJ | | 001-099 |
| 0577 | 24 | | GK | | 10-0 | 36-11-41 | D01600 | | 8 | | TB0177Y | C008 | BJ | | 115-199 |
| 0583 | 24 | | GK | | 6-0 | 73-21-12 | D05194 | | 5 | | D41637J | | 12 | | 001-099 |
| 0583 | 24 | | GK | | 5-0 | 73-21-12 | D05194 | | 5 | | D41637J | | 12 | | 115-199 |
| 0585 | 24 | | GK | | 6-0 | 73-21-12 | D05194 | | 4 | | D41637J | | 11 | | 001-099 |
| 0585 | 24 | | GK | | 5-0 | 73-21-12 | D05194 | | 4 | | D41637J | | 11 | | 115-199 |
| 0587 | 22 | | GK | | 6-0 | 76-11-21 | D05694 | | 6 | | TB0177X | B004 | BJ | | 001-099 |
| 0587 | 22 | | GK | | 10-0 | 76-11-21 | D05694 | | 6 | | TB0177X | B004 | BJ | | 115-199 |
| 0588 | 22 | | GK | | 6-0 | 76-11-21 | D05694 | | 8 | | TB0177X | C004 | BJ | | 001-099 |
| 0588 | 22 | | GK | | 10-0 | 76-11-21 | D05694 | | 8 | | TB0177X | C004 | BJ | | 115-199 |
| 0589 | 22 | | GK | | 6-0 | 76-11-21 | D05694 | | 7 | | TB0178Z | | 11 | BJ | 001-099 |
| 0589 | 22 | | GK | | 9-0 | 76-11-21 | D05694 | | 7 | | TB0178Z | | 21 | BJ | 115-199 |
| 0590 | 22 | | GK | | 6-0 | 76-11-21 | D05694 | | 3 | | D41616J | | 3 | | 001-099 |
| 0590 | 22 | | GK | | 8-0 | 76-11-21 | D05694 | | 3 | | D41616J | | 3 | | 115-199 |
| 0591 | 20 | | GK | | 9-0 | 27-62-11 | TB0178Y | | C023 | BJ | TB0173C | C013 | 2 | | 115-199 |
| 0592 | 20 | | GK | | 1-0 | 27-62-11 | TB0173B | | A012 | 2 | TB0173A | A011 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0592 | 20 | | GK | | 4-0 | 27-62-11 | TB0173B | A014 | 2 | | TB0173C | A013 | 2 | | 115-199 |
| 0595 | 20 | | GK | | 6-0 | 27-62-11 | D41030J | | 15 | | TB0173B | C012 | 2 | | 001-099 |
| 0595 | 20 | | GK | | 6-0 | 27-62-11 | D41030J | | 15 | | TB0173B | C014 | 2 | | 115-199 |
| 0614 | 22 | | GK | | 4-0 | 21-58-15 | D41034J | | 17 | | K00344 | 11 | C | | 001-099 |
| 0614 | 22 | | GK | | 7-0 | 21-58-15 | K00344 | | 11 | C | D41034J | 8 | | | 115-199 |
| 0615 | 18 | | GK | | 5-0 | 24-51-25 | D41408J | | 30 | | D40912J | 43 | | | 001-099 |
| 0615 | 18 | | GK | | 6-0 | 24-51-25 | D41408J | | 30 | | D40912J | 43 | | | 115-199 |
| 0616 | 22 | | GK | | 7-0 | 33-22-11 | D40718J | | 27 | | TB0179Y | C014 | BJ | | 001-099 |
| 0616 | 22 | | GK | | 9-0 | 33-22-11 | D41408J | | 7 | | TB0179Y | C014 | BJ | | 115-199 |
| 0618 | 22 | | GK | | 7-0 | 33-51-11 | D07080 | | A1 | | D41858J | 7 | | | ALL |
| 0619 | 22 | | GK | | 8-0 | 33-51-11 | D07080 | | A2 | * | D40718J | 15 | | | ALL |
| 0621 | 22 | | GK | | 8-0 | 33-51-11 | D07080 | | A3 | | D40718J | 13 | | | ALL |
| 0622 | 22 | | GK | | 7-0 | 33-51-11 | D07080 | | B1 | | D41858J | 6 | | | ALL |
| 0623 | 22 | | GK | | 8-0 | 33-51-11 | D07080 | | B3 | | D40718J | 14 | | | ALL |
| 0624 | 22 | | GK | | 1-0 | 33-21-51 | D07080 | | X1 | * | D07080 | C1 | | | 001-099 |
| 0624 | 22 | | GK | | 1-0 | 33-21-51 | D07080 | | C1 | | D07080 | X1 | | * | 115-199 |
| 0625 | 22 | | GK | | 9-0 | 33-21-51 | D07080 | | C2 | | D41408J | 9 | | | ALL |
| 0627 | 16 | | GK | | 8-0 | 33-26-11 | D07080 | | D1 | | D40718J | 22 | 16 | | 001-099 |
| 0627 | 22 | | GK | | 8-0 | 33-26-11 | D07080 | | D1 | | D40718J | 22 | | | 115-199 |
| 0628 | 16 | | GK | | 7-0 | 33-26-11 | D07080 | | D2 | | SM00008 | | WI | | 001-099 |
| 0628 | 22 | | GK | | 9-0 | 33-26-11 | D07080 | | D2 | | TB0178Z | 17 | BJ | | 115-199 |
| 0629 | 22 | | GK | | 9-0 | 33-21-51 | D07080 | | X1 | * | D41408J | 10 | | | ALL |
| 0630 | 24 | | GK | | 3-0 | 33-51-11 | D07080 | | X2 | | TB0179Y | C014 | BJ | | 001-099 |
| 0630 | 24 | | GK | | 4-0 | 33-51-11 | D07080 | | X2 | | TB0179Y | C014 | BJ | | 115-199 |
| 0631 | 24 | | GK | | 9-0 | 33-51-11 | D40718J | | 10 | | TB0179Y | C014 | BJ | | 001-099 |
| 0631 | 24 | | GK | | 8-0 | 33-51-11 | D40718J | | 10 | | TB0179Y | C014 | BJ | | 115-199 |
| 0637 | 22 | | GK | | 5-0 | 36-11-21 | TB0178Z | | 1 | BJ | D41032J | 40 | | | 001-099 |
| 0637 | 22 | | GK | | 5-0 | 36-11-21 | D41032J | | 40 | | TB0178Y | A019 | BJ | | 115-199 |
| 0638 | 24 | | GK | | 9-0 | 21-25-11 | D41852J | | 18 | | TB0170A | C007 | 2 | * | ALL |
| 0639 | 24 | | GK | | 7-0 | 21-25-11 | K00416 | | 13 | C | D41030J | 7 | | | ALL |
| 0641 | 24 | | GK | | 7-0 | 21-25-11 | D05188 | | 6 | | D41854J | 20 | | | ALL |
| 0642 | 24 | | GK | | 7-0 | 21-25-11 | D41030J | | 43 | | TB0170A | C007 | 2 | | ALL |
| 0643 | 24 | | GK | | 8-0 | 21-25-11 | D40570J | | 29 | | TB0170A | A007 | 2 | | 001-099 |
| 0643 | 24 | | GK | | 9-0 | 21-25-11 | D40570J | | 29 | | TB0170A | A007 | 2 | | 115-199 |
| 0644 | 24 | | GK | | 7-0 | 21-25-11 | D05188 | | 8 | | D41854J | 21 | | | ALL |
| 0645 | 22 | | GK | | 5-0 | 21-25-11 | K00416 | | 14 | C | GD01718 | DC.. | F | | ALL |
| 0646 | 24 | | GK | | 6-0 | 21-25-11 | D40050J | | 12 | | D41030J | 8 | | | ALL |
| 0647 | 24 | | GK | | 6-0 | 21-58-13 | K00344 | | 14 | C | TB0178A | C038 | 2 | | ALL |
| 0648 | 22 | | GK | | 5-0 | 21-51-21 | K00416 | | 12 | C | GD01718 | DC.. | F | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0649 | 24 | | GK | | 8-0 | 21-58-12 | D40570J | | 49 | | | D04316 | 6 | | | 001-099 |
| 0649 | 24 | | GK | | 7-0 | 21-58-12 | D40570J | | 49 | | | D04316 | 6 | | | 115-199 |
| 0650 | 24 | | GK | | 6-0 | 21-58-12 | D41032J | | 12 | | | TB0178A | A038 | 2 | | ALL |
| 0651 | 20 | | GK | | 6-0 | 21-58-13 | D41032J | | 19 | | | D40050J | 3 | | * | ALL |
| 0652 | 24 | | GK | | 9-0 | 21-58-12 | D00574 | | 1 | | | D40570J | 27 | | | ALL |
| 0654 | 24 | | GK | | 4-0 | 21-58-12 | D00574 | | 7 | | | TB0170A | C005 | 2 | | ALL |
| 0655 | 24 | | GK | | 4-0 | 21-58-12 | TB0170A | | A005 | 2 | | GD01702 | DC.. | 2 | | ALL |
| 0658 | 24 | | GK | | 4-0 | 21-58-12 | M10688 | | B | C | | TB0172A | A013 | 2 | | 001-099 |
| 0658 | 24 | | GK | | 11-0 | 21-58-12 | M10688 | | B | C | | TB0172A | A013 | 2 | | 115-199 |
| 0659 | 24 | | GK | | 8-0 | 21-58-12 | D00612 | | 9 | | | TB0172A | C013 | 2 | | 001-099 |
| 0659 | 24 | | GK | | 12-0 | 21-58-12 | D00612 | | 9 | | | TB0172A | C013 | 2 | | 115-199 |
| 0660 | 24 | | GK | | 7-0 | 21-58-12 | D00612 | | 11 | | | D41854J | 7 | | | 001-099 |
| 0660 | 24 | | GK | | 8-0 | 21-58-12 | D00612 | | 11 | | | D41854J | 7 | | | 115-199 |
| 0661 | 24 | | GK | | 8-0 | 21-58-12 | D00574 | | 2 | | | M10688 | A | C | | 001-099 |
| 0661 | 24 | | GK | | 11-0 | 21-58-12 | D00574 | | 2 | | | M10688 | A | C | | 115-199 |
| 0663 | 24 | | GK | | 6-0 | 21-58-13 | K00344 | | 13 | C | | D41030J | 48 | | | 115-199 |
| 0664 | 24 | | GK | | 6-0 | 21-58-13 | K00344 | | 13 | C | | D41858J | 4 | | | ALL |
| 0665 | 20 | | GK | | 6-0 | 21-58-13 | D40050J | | 3 | | * | D41032J | 17 | | | ALL |
| 0667 | 20 | | GK | | 7-0 | 21-58-21 | D41030J | | 51 | | | D04208 | 5 | | | 001-099 |
| 0667 | 20 | | GK | | 8-0 | 21-58-21 | D41030J | | 51 | | | D04208 | 5 | | | 115-199 |
| 0668 | 20 | | GK | | 7-0 | 21-58-21 | D41030J | | 52 | | | D04208 | 2 | | | 001-099 |
| 0668 | 20 | | GK | | 8-0 | 21-58-21 | D41030J | | 52 | | | D04208 | 2 | | | 115-199 |
| 0669 | 24 | | GK | | 7-0 | 21-58-21 | D41854J | | 16 | | | TB0170A | C006 | 2 | | ALL |
| 0670 | 24 | | GK | | 4-0 | 21-58-21 | D04232 | | 13 | | | TB0170A | A006 | 2 | *2 | ALL |
| 0671 | 24 | | GK | | 4-0 | 21-58-21 | D04232 | | 12 | | | GD01702 | DC.. | 2 | | ALL |
| 0672 | 24 | | GK | | 4-0 | 21-58-21 | D04208 | | 3 | | | TB0170A | A006 | 2 | *1 | ALL |
| 0673 | 20 | | GK | | 9-0 | 21-58-21 | D40186J | | 7 | | | D04232 | X2 | | | ALL |
| 0676 | 20 | | GK | | 1-0 | 21-58-21 | D04232 | | X1 | | | D04232 | C1 | | * | ALL |
| 0677 | 22 | | GK | | 4-0 | 21-58-24 | D04212 | | 12 | | | GD01702 | DC.. | 2 | | 115-199 |
| 0678 | 22 | | GK | | 7-0 | 21-58-24 | D04212 | | 13 | | | D41030J | 47 | | | 115-199 |
| 0681 | 22 | | GK | | 2-0 | 21-58-24 | D04212 | | C1 | | * | D04212 | X1 | | | 115-199 |
| 0682 | 22 | | GK | | 5-0 | 21-58-15 | K00344 | | 12 | C | | GD01718 | DC.. | F | | 001-099 |
| 0682 | 22 | | GK | | 3-0 | 21-58-15 | K00344 | | 12 | C | | GD01718 | DC.. | F | | 115-199 |
| 0690 | 22 | | GK | | 4-0 | 78-34-21 | SM00029 | | | WI | | D41858J | CAP | Y | | 001-002 |
| 0690 | 22 | | GK | | 5-0 | 78-34-21 | D41858J | | CAP | Y | | SM00029 | | WI | | 115-199 |
| 0691 | 22 | | GK | | 7-0 | 78-34-21 | SM00029 | | | WI | | D00616 | A1 | | | 001-002 |
| 0691 | 22 | | GK | | 8-0 | 78-34-21 | D00616 | | A1 | | | SM00029 | | WI | | 115-199 |
| 0699 | 22 | | GK | | 3-0 | 38-14-11 | D40718J | | 41 | | | SM00032 | | WI | | 001-099 |
| 0700 | 24 | | GK | | 2-0 | 23-31-13 | D02638 | | B3 | | | GD01714 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0700 | 24 | | GK | | 4-0 | 23-31-13 | D02638 | | B3 | | GD01714 | DC.. | 2 | | 115-199 |
| 0701 | 24 | | GK | | 8-0 | 23-31-13 | D02638 | | B2 | | D41030J | 11 | | | 001-099 |
| 0701 | 24 | | GK | | 6-0 | 23-31-13 | D02638 | | B2 | | D41030J | 11 | | | 115-199 |
| 0706 | 22 | | GK | | 5-0 | 30-11-11 | D42010J | | 34 | | TB0178Y | A004 | BJ | | ALL |
| 0708 | 22 | | GK | | 6-0 | 31-31-01 | D02638 | | A1 | | TB0178Y | C039 | BJ | | 001-099 |
| 0708 | 22 | | GK | | 5-0 | 31-31-13 | D02638 | | A1 | | TB0178Y | C011 | BJ | | 115-199 |
| 0709 | 22 | | GK | | 6-0 | 31-31-01 | D02638 | | A2 | | TB0178Y | A039 | BJ | | 001-099 |
| 0709 | 22 | | GK | | 7-0 | 31-31-13 | D02638 | | A2 | | D41739J | 6 | | | 115-199 |
| 0710 | 20 | | GK | | 5-0 | 74-31-21 | D41994J | | 18 | | TB0178Y | A027 | BJ | | 001-099 |
| 0710 | 22 | | GK | | 7-0 | 74-31-21 | D41994J | | 18 | | TB0174Y | C001 | BJ | | 115-199 |
| 0711 | 20 | | GK | | 6-0 | 74-31-21 | D04498 | | A1 | | TB0178Y | A027 | BJ | | 001-099 |
| 0711 | 22 | | GK | | 4-0 | 74-31-21 | D04498 | | A1 | | TB0174Y | C001 | BJ | | 115-199 |
| 0712 | 20 | | GK | | 6-0 | 74-31-21 | TB0178Y | | C007 | BJ | D04498 | A2 | | | 001-099 |
| 0712 | 22 | | GK | | 4-0 | 74-31-21 | TB0174Y | | C018 | BJ | D04498 | A2 | | | 115-199 |
| 0713 | 20 | | GK | | 5-0 | 74-31-21 | D41994J | | 34 | | TB0178Y | A027 | BJ | | 001-099 |
| 0713 | 22 | | GK | | 4-0 | 74-31-21 | D02472 | | A2 | | TB0174Y | C001 | BJ | | 115-199 |
| 0714 | 22 | | GK | | 6-0 | 74-31-21 | D02472 | | A1 | | D41994J | 1 | | | 115-199 |
| 0715 | 22 | | GK | | 7-0 | 74-31-21 | TB0174Y | | C015 | BJ | D41994J | 2 | | | 115-199 |
| 0716 | 20 | | GK | | 3-0 | 74-31-21 | D02472 | | X2 | | GD01712 | DC.. | 2 | | 115-199 |
| 0717 | 20 | | GK | | 4-0 | 74-31-21 | D02472 | | X1 | | TB0174Y | A002 | BJ | | 115-199 |
| 0718 | 20 | | GK | | 4-0 | 74-31-21 | D02470 | | X1 | | TB0174Y | A002 | BJ | | 115-199 |
| 0719 | 20 | | GK | | 4-0 | 74-31-21 | D02470 | | X2 | | GD01712 | DC.. | 2 | | 115-199 |
| 0720 | 20 | | GK | | 6-0 | 74-31-21 | D42008J | | 2 | | TB0178Y | C026 | BJ | | 001-099 |
| 0720 | 20 | | GK | | 4-0 | 74-31-21 | D02470 | | A2 | | TB0174Y | C002 | BJ | | 115-199 |
| 0721 | 20 | | GK | | 6-0 | 74-31-21 | D42008J | | 12 | | TB0178Y | C026 | BJ | | 001-099 |
| 0721 | 20 | | GK | | 7-0 | 74-31-21 | D42008J | | 12 | | TB0174Y | C002 | BJ | | 115-199 |
| 0722 | 20 | | GK | | 6-0 | 74-31-21 | D04498 | | D1 | | TB0178Y | C026 | BJ | | 001-099 |
| 0722 | 20 | | GK | | 7-0 | 74-31-21 | D04498 | | D1 | | TB0174Y | C002 | BJ | | 115-199 |
| 0723 | 20 | | GK | | 7-0 | 74-31-21 | D02470 | | A1 | | D42008J | 2 | | | 115-199 |
| 0724 | 18 | | GK | | 3-0 | 75-31-11 | D02630 | | A2 | | TB0174G | 8 | 2 | | 001-099 |
| 0724 | 18 | | GK | | 4-0 | 75-31-11 | D02630 | | A2 | | TB0174G | 3 | 2 | | 115-199 |
| 0725 | 18 | | GK | | 7-0 | 75-31-11 | D41998J | | 1 | | D02630 | A1 | | | 001-099 |
| 0725 | 18 | | GK | | 6-0 | 75-31-11 | D02630 | | A1 | | D41998J | 1 | | | 115-199 |
| 0726 | 16 | | GK | | 7-0 | 75-31-11 | D40738J | | 20 | | TB0174G | 8 | 2 | | 001-099 |
| 0726 | 16 | | GK | | 6-0 | 75-31-11 | D40738J | | 20 | | TB0174G | 3 | 2 | | 115-199 |
| 0727 | 16 | | GK | | 7-0 | 75-31-11 | D41998J | | 2 | | TB0174G | 8 | 2 | | 001-099 |
| 0727 | 16 | | GK | | 7-0 | 75-31-11 | TB0174G | | 3 | 2 | D41998J | 2 | | | 115-199 |
| 0728 | 22 | | GK | | 7-0 | 76-11-12 | D02630 | | B2 | | D42010J | 4 | | | 001-099 |
| 0728 | 22 | | GK | | 6-0 | 76-11-12 | D02630 | | B2 | | D42010J | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0729 | 22 | | GK | | 7-0 | 76-11-12 | D02630 | | B1 | | D41994J | 6 | | | 001-099 |
| 0729 | 22 | | GK | | 6-0 | 76-11-12 | D02630 | | B1 | | D41994J | 6 | | | 115-199 |
| 0730 | 22 | | GK | | 7-0 | 76-11-12 | D02630 | | C1 | | D41994J | 7 | | | 001-099 |
| 0730 | 22 | | GK | | 6-0 | 76-11-12 | D02630 | | C1 | | D41994J | 7 | | | 115-199 |
| 0731 | 22 | | GK | | 3-0 | 80-11-21 | D02216 | | 4 | | D02638 | X2 | | * | 001-099 |
| 0731 | 22 | | GK | | 7-0 | 76-11-12 | D02216 | | 1 | | D42010J | 2 | | | 115-199 |
| 0732 | 24 | | GK | | 7-0 | 76-11-12 | D02216 | | 5 | | D42010J | 17 | | | ALL |
| 0733 | 22 | | GK | | 3-0 | 76-11-12 | D02216 | | 7 | | GD01713 | DC.. | 2 | | 001-099 |
| 0733 | 22 | | GK | | 4-0 | 76-11-12 | D02216 | | 7 | | GD01713 | DC.. | 2 | | 115-199 |
| 0734 | 20 | | GK | | 3-0 | 76-11-12 | D02216 | | 2 | | GD01713 | DC.. | 2 | | 001-099 |
| 0734 | 20 | | GK | | 4-0 | 76-11-12 | D02216 | | 2 | | GD01713 | DC.. | 2 | | 115-199 |
| 0736 | 24 | | GK | | 7-0 | 76-11-12 | D02216 | | 6 | | TB0178Y | C027 | BJ | | 001-099 |
| 0736 | 24 | | GK | | 4-0 | 76-11-12 | D02216 | | 6 | | TB0174Y | A005 | BJ | | 115-199 |
| 0738 | 24 | | GK | | 5-0 | 76-11-12 | D42010J | | 18 | | TB0178Y | C027 | BJ | | 001-099 |
| 0738 | 24 | | GK | | 7-0 | 76-11-12 | D42010J | | 18 | | TB0174Y | A005 | BJ | | 115-199 |
| 0739 | 24 | | GK | | 5-0 | 76-11-12 | D42010J | | 3 | | TB0178Y | C027 | BJ | | 001-099 |
| 0739 | 24 | | GK | | 7-0 | 76-11-12 | D42010J | | 3 | | TB0174Y | A005 | BJ | | 115-199 |
| 0740 | 22 | | GK | | 7-0 | 76-11-12 | D02216 | | 8 | | D42010J | 1 | | | 001-099 |
| 0740 | 22 | | GK | | 7-0 | 76-11-12 | SM00049 | | | WI | D42010J | 1 | | | 115-199 |
| 0741 | 22 | | GK | | 4-6 | 76-11-12 | D02220 | | 7 | | GD01713 | DC.. | 2 | | 115-199 |
| 0743 | 22 | | GK | | 7-0 | 76-11-21 | D01814 | | A2 | | D41994J | 3 | | | ALL |
| 0744 | 22 | | GK | | 6-0 | 76-11-21 | D01814 | | A1 | | TB0178Z | 11 | BJ | | 001-099 |
| 0744 | 22 | | GK | | 5-0 | 76-11-21 | D01814 | | A1 | | TB0178Z | 21 | BJ | | 115-199 |
| 0745 | 22 | | GK | | 6-0 | 76-11-21 | D01814 | | X1 | | TB0178X | B022 | BJ | | 001-099 |
| 0745 | 22 | | GK | | 5-0 | 76-11-21 | D01814 | | X1 | | TB0178X | D005 | BJ | | 115-199 |
| 0746 | 20 | | GK | | 3-0 | 76-11-21 | D01814 | | X2 | | GD01714 | DC.. | 2 | | ALL |
| 0747 | 22 | | GK | | 6-0 | 78-34-21 | D02640 | | A3 | | TB0178Z | 2 | BJ | | 001-002 |
| 0747 | 22 | | GK | | 5-0 | 78-34-21 | D02640 | | A3 | | TB0174Y | C019 | BJ | | 003-099 |
| 0747 | 22 | | GK | | 4-0 | 78-34-21 | D02640 | | A3 | | TB0174Y | C005 | BJ | | 115-199 |
| 0748 | 22 | | GK | | 9-0 | 78-34-21 | D41478J | | 17 | | M10010 | A | C | | 003-099 |
| 0749 | 22 | | GK | | 1-0 | 78-34-21 | D02640 | | A2 | | D02640 | X1 | | * | ALL |
| 0750 | 22 | | GK | | 7-0 | 78-34-21 | D02640 | | X1 | * | D42010J | 8 | | | 001-099 |
| 0750 | 22 | | GK | | 9-0 | 78-34-21 | D02640 | | X1 | * | D42010J | 8 | | | 115-199 |
| 0751 | 22 | | GK | | 7-0 | 78-34-21 | D02640 | | X2 | | D42010J | 7 | | | 001-099 |
| 0751 | 22 | | GK | | 9-0 | 78-34-21 | D02640 | | X2 | | D42010J | 7 | | | 115-199 |
| 0754 | 24 | | GK | | 5-0 | 78-36-21 | D41994J | | 35 | | D41994J | 8 | | | 001-002 |
| 0754 | 24 | | GK | | 1-0 | 78-36-21 | D41994J | | 35 | | D41994J | 51 | | | 003-099 |
| 0754 | 24 | | GK | | 7-0 | 78-36-21 | D41994J | | 17 | | D41994J | 8 | | | 115-199 |
| 0758 | 24 | | GK | | 5-0 | 78-36-21 | D40738J | | 9 | | TB0178Y | A029 | BJ | | 001-002 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0758 | 24 | | GK | | 3-0 | 78-36-21 | D40738J | | 15 | | SM00013 | | WI | | 003-099 |
| 0758 | 24 | | GK | | 9-0 | 78-36-21 | D40738J | | 9 | | TB0174Y | A006 | BJ | | 115-199 |
| 0759 | 24 | | GK | | 5-0 | 78-36-21 | D41994J | | 36 | | TB0178Y | A029 | BJ | | 001-002 |
| 0759 | 24 | | GK | | 3-0 | 78-36-21 | D41994J | | 36 | | SM00013 | | WI | | 003-099 |
| 0759 | 24 | | GK | | 7-0 | 78-36-21 | D41994J | | 16 | | TB0174Y | A006 | BJ | | 115-199 |
| 0768 | 24 | | GK | | 4-0 | 78-36-21 | D41994J | | 8 | | D41478J | 21 | | | 003-099 |
| 0773 | 20 | | GK | | 5-0 | 80-11-21 | D40738J | | 11 | | TB0178Y | C009 | BJ | | 001-099 |
| 0773 | 20 | | GK | | 7-0 | 80-11-21 | D40738J | | 11 | | TB0174Z | 11 | BJ | | 115-199 |
| 0774 | 24 | | GK | | 1-0 | 80-11-21 | TB0174A | A001 | 2 | | TB0174A | A002 | 2 | | 001-099 |
| 0774 | 24 | | GK | | 1-0 | 80-11-21 | TB0174A | A004 | 2 | | TB0174A | A008 | 2 | | 115-199 |
| 0775 | 20 | | GK | | 3-0 | 80-11-21 | D02638 | | X1 | | D04498 | X1 | | * | 001-099 |
| 0775 | 20 | | GK | | 4-0 | 80-11-21 | D02638 | | X1 | | TB0174Z | 11 | BJ | | 115-199 |
| 0776 | 20 | | GK | | 3-0 | 80-11-21 | D02632 | | 6 | | D02638 | X1 | | * | 001-099 |
| 0776 | 20 | | GK | | 3-0 | 80-11-21 | D02632 | | 6 | | TB0174Z | 11 | BJ | | 115-199 |
| 0777 | 20 | | GK | | 4-0 | 80-11-21 | D03052 | | X1 | | TB0174Z | 11 | BJ | | 115-199 |
| 0778 | 20 | | GK | | 4-0 | 80-11-21 | D03052 | | A2 | | TB0174Z | 11 | BJ | | 115-199 |
| 0779 | 20 | | GK | | 4-0 | 80-11-21 | D03052 | | A3 | | TB0174Y | A002 | BJ | | 115-199 |
| 0780 | 20 | | GK | | 5-0 | 80-11-21 | TB0178Y | C009 | BJ | | D41994J | 10 | | | 001-099 |
| 0780 | 20 | | GK | | 7-0 | 80-11-21 | D03052 | | A1 | | D41994J | 10 | | | 115-199 |
| 0781 | 20 | | GK | | 7-0 | 80-11-21 | D41994J | | 11 | | TB0174Y | C009 | BJ | | ALL |
| 0782 | 20 | | GK | | 4-0 | 80-11-21 | D02630 | | C2 | | TB0174Y | C009 | BJ | | ALL |
| 0784 | 20 | | GK | | 7-0 | 80-11-21 | D41994J | | 12 | | TB0174Y | A003 | BJ | | 001-099 |
| 0784 | 20 | | GK | | 7-0 | 80-11-21 | D41994J | | 12 | | TB0174Y | A010 | BJ | | 115-199 |
| 0785 | 20 | | GK | | 3-0 | 80-11-21 | D03054 | | X1 | | TB0174Y | A003 | BJ | | 001-099 |
| 0785 | 20 | | GK | | 4-0 | 80-11-21 | D03054 | | X1 | | TB0174Y | A010 | BJ | | 115-199 |
| 0786 | 20 | | GK | | 3-0 | 80-11-21 | D03056 | | 6 | | TB0174Y | A003 | BJ | | 001-099 |
| 0786 | 20 | | GK | | 3-0 | 80-11-21 | D03056 | | 6 | | TB0174Y | A010 | BJ | | 115-199 |
| 0787 | 20 | | GK | | 8-0 | 80-11-21 | D42008J | | 5 | | TB0174Y | A003 | BJ | | 001-099 |
| 0787 | 20 | | GK | | 7-0 | 80-11-21 | D42008J | | 5 | | TB0174Y | A010 | BJ | | 115-199 |
| 0788 | 24 | | GK | | 7-0 | 80-11-21 | D41994J | | 13 | | TB0174A | A001 | 2 | | 001-099 |
| 0788 | 24 | | GK | | 7-0 | 80-11-21 | D41994J | | 13 | | TB0174A | A004 | 2 | | 115-199 |
| 0789 | 24 | | GK | | 3-0 | 80-11-21 | M10335 | | A | C | TB0174A | C001 | 2 | | 001-099 |
| 0789 | 24 | | GK | | 3-0 | 80-11-21 | M10335 | | A | C | TB0174A | C004 | 2 | | 115-199 |
| 0790 | 24 | | GK | | 3-0 | 80-11-21 | D03056 | | 7 | | TB0174A | C002 | 2 | | 001-099 |
| 0790 | 24 | | GK | | 3-0 | 80-11-21 | D03056 | | 7 | | TB0174A | C008 | 2 | | 115-199 |
| 0791 | 24 | | GK | | 8-0 | 80-11-21 | D42008J | | 7 | | TB0174A | C002 | 2 | | 001-099 |
| 0791 | 24 | | GK | | 7-0 | 80-11-21 | D42008J | | 7 | | TB0174A | C008 | 2 | | 115-199 |
| 0792 | 24 | | GK | | 7-0 | 80-11-21 | D42008J | | 8 | | TB0174Y | A009 | BJ | | 115-199 |
| 0793 | 24 | | GK | | 8-0 | 80-11-21 | M10335 | | B | C | D42008J | 8 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 22

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0793 | 24 | | GK | | 3-0 | 80-11-21 | M10335 | | B | C | TB0174Y | A009 | BJ | | 115-199 |
| 0794 | 24 | | GK | | 3-0 | 80-11-21 | D02632 | | 4 | | M10335 | B | C | | 001-099 |
| 0794 | 24 | | GK | | 3-0 | 80-11-21 | D02632 | | 4 | | TB0174Y | A009 | BJ | | 115-199 |
| 0795 | 20 | | GK | | 3-0 | 80-11-21 | D03054 | | X2 | | GD01713 | DC.. | 2 | | 001-099 |
| 0795 | 20 | | GK | | 4-0 | 80-11-21 | D03054 | | X2 | | GD01714 | DC.. | 2 | | 115-199 |
| 0796 | 20 | | GK | | 3-0 | 80-11-21 | D03056 | | 11 | | GD01715 | DC.. | 2 | | 001-099 |
| 0796 | 20 | | GK | | 3-0 | 80-11-21 | D03056 | | 11 | | GD01714 | DC.. | 2 | | 115-199 |
| 0797 | 20 | | GK | | 3-0 | 80-11-21 | D02638 | | X2 | * | D03056 | 10 | | | 001-099 |
| 0797 | 20 | | GK | | 4-0 | 80-11-21 | D02638 | | X2 | | TB0174Y | C010 | BJ | | 115-199 |
| 0798 | 20 | | GK | | 3-0 | 80-11-21 | D03056 | | 10 | | TB0174Y | C010 | BJ | | 115-199 |
| 0799 | 24 | | GK | | 2-0 | 80-11-21 | D03056 | | 14 | | D02632 | 8 | | | 001-099 |
| 0799 | 20 | | GK | | 2-0 | 80-11-21 | D03056 | | 14 | | D02632 | 8 | | | 115-199 |
| 0800 | 24 | | GK | | 2-0 | 80-11-21 | D03056 | | 8 | | D02632 | 14 | | | ALL |
| 0801 | 20 | | GK | | 3-0 | 80-11-21 | D03056 | | 12 | | GD01715 | DC.. | 2 | | 001-099 |
| 0801 | 20 | | GK | | 3-0 | 80-11-21 | D03056 | | 12 | | GD01714 | DC.. | 2 | | 115-199 |
| 0802 | 20 | | GK | | 3-0 | 80-11-21 | D02630 | | X2 | | GD01714 | DC.. | 2 | | 001-099 |
| 0802 | 20 | | GK | | 4-0 | 80-11-21 | D02630 | | X2 | | GD01714 | DC.. | 2 | | 115-199 |
| 0803 | 20 | | GK | | 7-0 | 80-11-21 | D02632 | | 5 | | D42010J | 9 | | | ALL |
| 0804 | 20 | | GK | | 3-0 | 80-11-21 | D02630 | | X1 | | TB0174Y | C009 | BJ | | 001-099 |
| 0804 | 20 | | GK | | 4-0 | 80-11-21 | TB0174Y | | C009 | BJ | D02630 | X1 | | | 115-199 |
| 0805 | 20 | | GK | | 7-0 | 80-11-21 | D42008J | | 4 | | D03052 | X2 | | | 115-199 |
| 0806 | 20 | | GK | | 8-0 | 80-11-21 | D42008J | | 6 | | D02632 | 12 | | | 001-099 |
| 0806 | 20 | | GK | | 7-0 | 80-11-21 | D42008J | | 6 | | D02632 | 12 | | | 115-199 |
| 0807 | 24 | | GK | | 3-0 | 80-11-21 | GD01715 | | DC.. | 2 | D02632 | 7 | | | 001-099 |
| 0807 | 20 | | GK | | 3-0 | 80-11-21 | GD01714 | | DC.. | 2 | D02632 | 7 | | | 115-199 |
| 0808 | 20 | | GK | | 7-0 | 74-31-21 | TB0174Y | | A015 | BJ | D42008J | 1 | | | 115-199 |
| 0809 | 20 | | GK | | 6-0 | 74-31-21 | D04498 | | D2 | | TB0178Y | A028 | BJ | | 001-099 |
| 0809 | 20 | | GK | | 4-0 | 74-31-21 | D04498 | | D2 | | TB0174Y | A018 | BJ | | 115-199 |
| 0810 | 24 | | GK | | 3-0 | 74-31-21 | D04228 | | A3 | | GD01713 | DC.. | 2 | | 001-099 |
| 0810 | 24 | | GK | | 4-0 | 74-31-21 | D04228 | | A3 | | GD01714 | DC.. | 2 | | 115-199 |
| 0811 | 24 | | GK | | 7-0 | 74-31-21 | D04228 | | A2 | | D42010J | 16 | | | 001-099 |
| 0811 | 24 | | GK | | 6-0 | 74-31-21 | D04228 | | A2 | | D42008J | 14 | | | 115-199 |
| 0812 | 20 | | GK | | 7-0 | 74-31-21 | D04228 | | B3 | | D40738J | 8 | | | 001-099 |
| 0812 | 20 | | GK | | 5-0 | 74-31-21 | D04228 | | B3 | | D40738J | 8 | | | 115-199 |
| 0813 | 20 | | GK | | 8-0 | 74-31-21 | D04228 | | B2 | | D42008J | 13 | | | 001-099 |
| 0813 | 20 | | GK | | 6-0 | 74-31-21 | D04228 | | B2 | | D42008J | 13 | | | 115-199 |
| 0814 | 20 | | GK | | 1-0 | 74-31-21 | D04228 | | B1 | | D04228 | X1 | | * | 001-099 |
| 0814 | 20 | | GK | | 4-0 | 74-31-21 | D04228 | | B1 | | TB0174Y | A013 | BJ | | 115-199 |
| 0815 | 20 | | GK | | 7-0 | 74-31-21 | D04228 | | X1 | * | D40718J | 19 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 23

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0815 | 20 | | GK | | 4-0 | 74-31-21 | D04228 | | X1 | | TB0174Y | A013 | BJ | | 115-199 |
| 0816 | 20 | | GK | | 7-0 | 74-31-21 | D40718J | | 19 | | TB0174Y | A013 | BJ | | 115-199 |
| 0817 | 20 | | GK | | 3-0 | 74-31-21 | D04228 | | X2 | | GD01713 | AC.. | 2 | | 001-099 |
| 0817 | 20 | | GK | | 4-0 | 74-31-21 | D04228 | | X2 | | GD01714 | AC.. | 2 | | 115-199 |
| 0818 | 20 | | GK | | 8-0 | 74-31-21 | D04498 | | X2 | | D41616J | 8 | | | 001-099 |
| 0818 | 20 | | GK | | 4-0 | 74-31-21 | D04498 | | X2 | | TB0174Y | A014 | BJ | | 115-199 |
| 0819 | 20 | | GK | | 7-0 | 74-31-21 | D41616J | | 10 | | TB0174Y | A014 | BJ | | 115-199 |
| 0820 | 20 | | GK | | 7-0 | 74-31-21 | D41616J | | 8 | | TB0174Y | A014 | BJ | | 115-199 |
| 0821 | 20 | | GK | | 4-0 | 76-11-12 | D02216 | | 4 | | TB0174Y | C010 | BJ | | 115-199 |
| 0822 | 22 | | GK | | 7-0 | 77-12-41 | D40570J | | 22 | | TB0174Y | C013 | BJ | | 115-199 |
| 0823 | 22 | | GK | | 7-0 | 77-12-41 | D04314 | | X1 | * | D40570J | 22 | | | 001-099 |
| 0823 | 22 | | GK | | 4-0 | 77-12-41 | D04314 | | X1 | | TB0174Y | C013 | BJ | | 115-199 |
| 0824 | 22 | | GK | | 3-0 | 77-12-41 | D04316 | | 3 | | D04314 | X1 | | * | 001-099 |
| 0824 | 22 | | GK | | 3-0 | 77-12-41 | D04316 | | 3 | | TB0174Y | C013 | BJ | | 115-199 |
| 0825 | 22 | | GK | | 3-0 | 77-12-41 | D04314 | | X2 | | GD01715 | DC.. | 2 | | 001-099 |
| 0825 | 22 | | GK | | 4-0 | 77-12-41 | D04314 | | X2 | | GD01713 | DC.. | 2 | | 115-199 |
| 0826 | 22 | | GK | | 4-0 | 77-12-41 | D04316 | | 7 | | GD01715 | DC.. | 2 | | 001-099 |
| 0826 | 22 | | GK | | 4-0 | 77-12-41 | D04316 | | 7 | | GD01713 | DC.. | 2 | | 115-199 |
| 0827 | 22 | | GK | | 3-0 | 77-12-42 | D04244 | | X1 | | TB0174Y | C004 | BJ | | 001-099 |
| 0827 | 22 | | GK | | 4-0 | 77-12-42 | D04244 | | X1 | | TB0174Y | C014 | BJ | | 115-199 |
| 0828 | 22 | | GK | | 7-0 | 77-12-42 | D42010J | | 12 | | TB0174Y | C004 | BJ | | 001-099 |
| 0828 | 22 | | GK | | 7-0 | 77-12-42 | D42010J | | 12 | | TB0174Y | C014 | BJ | | 115-199 |
| 0829 | 22 | | GK | | 7-0 | 77-12-42 | D42010J | | 15 | | TB0174Y | C004 | BJ | | 001-099 |
| 0829 | 22 | | GK | | 7-0 | 77-12-42 | D42010J | | 15 | | TB0174Y | C014 | BJ | | 115-199 |
| 0830 | 22 | | GK | | 3-0 | 77-12-42 | D04246 | | 3 | | TB0174Y | C004 | BJ | | 001-099 |
| 0830 | 22 | | GK | | 4-0 | 77-12-42 | D04246 | | 3 | | TB0174Y | C014 | BJ | | 115-199 |
| 0831 | 22 | | GK | | 4-0 | 77-12-42 | D04244 | | X2 | | GD01713 | DC.. | 2 | | ALL |
| 0832 | 22 | | GK | | 4-0 | 77-12-42 | D04246 | | 7 | | GD01715 | DC.. | 2 | | 001-099 |
| 0832 | 22 | | GK | | 4-0 | 77-12-42 | D04246 | | 7 | | GD01714 | DC.. | 2 | | 115-199 |
| 0837 | 22 | | GK | | 6-0 | 78-34-21 | D42008J | | 3 | | TB0178Z | 2 | BJ | | 001-002 |
| 0837 | 22 | | GK | | 6-0 | 78-34-21 | D42008J | | 3 | | TB0174Y | C019 | BJ | | 003-099 |
| 0837 | 22 | | GK | | 7-0 | 78-34-21 | D42008J | | 3 | | TB0174Y | C005 | BJ | | 115-199 |
| 0838 | 20 | | GK | | 6-0 | 80-11-21 | D04498 | | X1 | * | TB0178Y | C009 | BJ | | 001-099 |
| 0838 | 20 | | GK | | 4-0 | 80-11-21 | D04498 | | X1 | | TB0174Z | 11 | BJ | | 115-199 |
| 0839 | 24 | | GK | | 5-0 | 30-33-11 | D04316 | | 5 | | TB0178Y | A010 | BJ | | 115-199 |
| 0840 | 24 | | GK | | 10-0 | 30-33-11 | D04316 | | 4 | | D03212 | B1 | | * | 001-099 |
| 0840 | 24 | | GK | | 5-0 | 30-33-11 | D04316 | | 4 | | TB0178Y | C010 | BJ | | 115-199 |
| 0841 | 24 | | GK | | 2-0 | 30-33-11 | D04316 | | 2 | | D04246 | 4 | | | 001-099 |
| 0841 | 24 | | GK | | 1-0 | 30-33-11 | D04316 | | 2 | | D04246 | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 24

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 0842 | 24 | | GK | | 10-0 | 30-33-11 | | D04246 | | 5 | | D03212 | B2 | | * | 001-099 | |
| 0842 | 24 | | GK | | 5-0 | 30-33-11 | | D04246 | | 5 | | TB0178Y | A010 | BJ | | 115-199 | |
| 0845 | 24 | | GK | | 3-0 | 30-31-12 | | D04244 | | A2 | | D04314 | A2 | | * | 001-099 | |
| 0845 | 24 | | GK | | 5-0 | 30-31-12 | | D04244 | | A2 | | TB0178Y | A009 | BJ | | 115-199 | |
| 0846 | 24 | | GK | | 3-0 | 30-31-12 | | D04314 | | A1 | | GD01715 | AC.. | 2 | | 001-099 | |
| 0846 | 24 | | GK | | 4-0 | 30-31-12 | | D04314 | | A1 | | GD01715 | AC.. | 2 | | 115-199 | |
| 0847 | 24 | | GK | | 10-0 | 30-31-12 | | D04314 | | A2 | * | D03212 | C2 | | * | 001-099 | |
| 0847 | 24 | | GK | | 5-0 | 30-31-12 | | D04314 | | A2 | | TB0178Y | A009 | BJ | | 115-199 | |
| 0848 | 20 | | GK | | 9-0 | 36-11-21 | | D03056 | | 3 | | D05194 | 11 | | | 001-099 | |
| 0848 | 20 | | GK | | 11-0 | 36-11-21 | | D03056 | | 3 | | D05194 | 11 | | | 115-199 | |
| 0849 | 20 | | GK | | 6-0 | 36-11-21 | | D03056 | | 5 | | TB0178Z | 1 | BJ | | 001-099 | |
| 0849 | 20 | | GK | | 5-0 | 36-11-21 | | D03056 | | 5 | | TB0178Y | A019 | BJ | | 115-199 | |
| 0850 | 20 | | GK | | 5-0 | 36-11-21 | | D03056 | | 4 | | TB0178Y | A003 | BJ | | 115-199 | |
| 0851 | 22 | | GK | | 6-0 | 30-21-11 | | D03054 | | C2 | | TB0178Y | C010 | BJ | | 001-099 | |
| 0851 | 22 | | GK | | 5-0 | 30-21-11 | | D03054 | | C2 | | TB0178Y | A027 | BJ | | 115-199 | |
| 0852 | 22 | | GK | | 7-0 | 30-21-11 | | D03054 | | C3 | | D41994J | 15 | | | 001-099 | |
| 0852 | 22 | | GK | | 6-0 | 30-21-11 | | D03054 | | C3 | | D41994J | 15 | | | 115-199 | |
| 0853 | 22 | | GK | | 6-0 | 76-11-21 | | D04248 | | 1 | | TB0178Z | 11 | BJ | | 001-099 | |
| 0853 | 22 | | GK | | 5-0 | 76-11-21 | | D04248 | | 1 | | TB0178Z | 21 | BJ | | 115-199 | |
| 0854 | 22 | | GK | | 6-0 | 76-11-21 | | D04248 | | 7 | | TB0178Z | 11 | BJ | | 001-099 | |
| 0854 | 22 | | GK | | 5-0 | 76-11-21 | | D04248 | | 7 | | TB0178Z | 21 | BJ | | 115-199 | |
| 0855 | 22 | | GK | | 8-0 | 76-11-21 | | D04248 | | 3 | | TB0177X | D004 | BJ | | ALL | |
| 0856 | 22 | | GK | | 8-0 | 76-11-21 | | D01814 | | A3 | | TB0177X | C004 | BJ | | 001-099 | |
| 0856 | 22 | | GK | | 8-0 | 76-11-21 | | TB0177X | C004 | BJ | | D01814 | A3 | | | 115-199 | |
| 0858 | 22 | | GK | | 7-0 | 49-61-11 | | D03054 | | B2 | | D41684J | 16 | | | ALL | |
| 0859 | 22 | | GK | | 7-0 | 49-61-11 | | D03054 | | B1 | | D41684J | 14 | | | ALL | |
| 0864 | 22 | | GK | | 6-0 | 29-22-11 | | D40570J | | 15 | | TB0178Y | C029 | BJ | | 001-099 | |
| 0864 | 22 | | GK | | 7-0 | 29-22-11 | | D40570J | | 15 | | TB0174Y | A016 | BJ | | 115-199 | |
| 0865 | 22 | | GK | | 7-0 | 29-22-11 | | D04314 | | C1 | | D40570J | 20 | | | ALL | |
| 0866 | 22 | | GK | | 6-0 | 29-22-11 | | D04664 | | A1 | | TB0178Y | A010 | BJ | | 001-099 | |
| 0866 | 22 | | GK | | 8-0 | 29-22-11 | | D04664 | | A1 | | TB0177Y | A006 | BJ | | 115-199 | |
| 0867 | 22 | | GK | | 6-0 | 29-22-11 | | D40570J | | 3 | | TB0178Y | A010 | BJ | | 001-099 | |
| 0867 | 22 | | GK | | 5-0 | 29-22-11 | | D40570J | | 3 | | TB0177Y | A006 | BJ | | 115-199 | |
| 0868 | 22 | | GK | | 7-0 | 29-22-11 | | D40570J | | 17 | | D04314 | C2 | | | ALL | |
| 0869 | 22 | | GK | | 6-0 | 29-22-11 | | D04664 | | A3 | | TB0178Y | C029 | BJ | | 001-099 | |
| 0869 | 22 | | GK | | 4-0 | 29-22-11 | | D04664 | | A3 | | TB0174Y | A016 | BJ | | 115-199 | |
| 0870 | 22 | | GK | | 6-0 | 29-22-11 | | D40570J | | 4 | | TB0178Y | C029 | BJ | | 001-099 | |
| 0870 | 22 | | GK | | 7-0 | 29-22-11 | | D40570J | | 4 | | TB0174Y | A016 | BJ | | 115-199 | |
| 0871 | 22 | | GK | | 7-0 | 29-22-11 | | D04314 | | C3 | * | D40570J | 18 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 25

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0899 | 20 | | GK | | 8-0 | 74-31-21 | D42008J | 11 | | | TB0174Y | A018 | BJ | | 115-199 |
| 0900 | 20 | | GK | | 5-0 | 74-31-21 | D41994J | 19 | | | TB0178Y | C007 | BJ | | 001-099 |
| 0900 | 20 | | GK | | 7-0 | 74-31-21 | D41994J | 19 | | | TB0174Y | C018 | BJ | | 115-199 |
| 0901 | 20 | | GK | | 6-0 | 74-31-21 | D40570J | 47 | | | TB0178Y | A028 | BJ | | 001-099 |
| 0901 | 20 | | GK | | 7-0 | 74-31-21 | D40570J | 47 | | | TB0174Y | A018 | BJ | | 115-199 |
| 0905 | 22 | | GK | | 7-0 | 29-22-11 | D40570J | 18 | | | TB0174Y | A019 | BJ | | 115-199 |
| 0906 | 22 | | GK | | 3-0 | 29-22-11 | D04664 | A2 | | | D04314 | C3 | | * | 001-099 |
| 0906 | 22 | | GK | | 5-0 | 29-22-11 | D04664 | A2 | | | TB0174Y | A019 | BJ | | 115-199 |
| 0907 | 20 | | GK | | 7-0 | 30-34-22 | D04244 | C2 | | * | D40718J | 23 | | | 001-099 |
| 0907 | 18 | | GK | | 5-0 | 30-34-22 | D04244 | C2 | | | TB0178G | 2 | 2 | | 115-199 |
| 0908 | 20 | | GK | | 8-0 | 30-34-22 | D04244 | C1 | | * | D42008J | 17 | | | 001-099 |
| 0908 | 18 | | GK | | 5-0 | 30-34-22 | D04244 | C1 | | | TB0178G | 1 | 2 | | 115-199 |
| 0909 | 22 | | GK | | 8-0 | 30-34-22 | D05422 | D2 | | | D41909J | 43 | | | 001-099 |
| 0909 | 22 | | GK | | 8-0 | 30-34-22 | D41909J | 43 | | | D05422 | D2 | | | 115-199 |
| 0910 | 22 | | GK | | 3-0 | 30-34-22 | D05422 | B2 | | | GD01712 | DC.. | 2 | | ALL |
| 0911 | 22 | | GK | | 8-0 | 30-34-22 | D05422 | D3 | | | D41909J | 44 | | | 001-099 |
| 0911 | 22 | | GK | | 8-0 | 30-34-22 | D41909J | 44 | | | D05422 | D3 | | | 115-199 |
| 0912 | 22 | | GK | | 7-0 | 30-34-22 | D05422 | A3 | | | D42176J | 8 | | | 001-099 |
| 0912 | 22 | | GK | | 7-0 | 30-34-22 | D42176J | 8 | | | D05422 | A3 | | | 115-199 |
| 0913 | 22 | | GK | | 3-0 | 30-34-22 | D05422 | C3 | | | GD01712 | DC.. | 2 | | ALL |
| 0914 | 22 | | GK | | 7-0 | 30-34-22 | D05422 | X1 | | | D40718J | 31 | | | 001-099 |
| 0914 | 22 | | GK | | 7-0 | 30-34-22 | D40718J | 31 | | | D05422 | X1 | | | 115-199 |
| 0915 | 22 | | GK | | 3-0 | 30-34-22 | D05422 | X2 | | | GD01712 | DC.. | 2 | | ALL |
| 0916 | 18 | | GK | | 8-0 | 30-34-22 | D05422 | C1 | | | D42008J | 18 | 18 | | 001-099 |
| 0916 | 18 | | GK | | 8-0 | 30-34-22 | D42008J | 18 | 18 | | D05422 | C1 | | | 115-199 |
| 0917 | 18 | | GK | | 3-0 | 30-34-22 | D05422 | B1 | | | GD01712 | AC.. | 2 | | ALL |
| 0924 | 24 | | GK | | 7-0 | 21-51-22 | D03008 | C1 | | | D40064J | 22 | | | 001-099 |
| 0932 | 22 | | GK | | 8-0 | 76-11-21 | D04248 | 6 | | | TB0177X | B004 | BJ | | ALL |
| 0936 | 24 | | GK | | 7-0 | 21-51-22 | D03008 | B1 | | | D40064J | 23 | | | 001-099 |
| 0937 | 24 | | GK | | 7-0 | 21-51-22 | D03008 | A1 | | | D40064J | 39 | | | 001-099 |
| 0938 | 24 | | GK | | 7-0 | 21-51-22 | D03006 | C1 | | | D40064J | 51 | | | 001-099 |
| 0939 | 24 | | GK | | 7-0 | 21-51-22 | D03006 | B1 | | | D40064J | 56 | | | 001-099 |
| 0940 | 24 | | GK | | 7-0 | 21-51-22 | D03006 | A1 | | | D40064J | 8 | | | 001-099 |
| 0941 | 24 | | GK | | 7-0 | 21-51-22 | D04096 | 1 | | | D40064J | 9 | | | 001-099 |
| 0942 | 24 | | GK | | 1-0 | 21-51-22 | D03008 | X2 | | * | D03006 | X2 | | * | 001-099 |
| 0943 | 24 | | GK | | 1-0 | 21-51-22 | D03008 | X1 | | * | D03006 | X1 | | * | 001-099 |
| 0944 | 24 | | GK | | 3-0 | 21-51-22 | D03008 | X1 | | * | D04096 | 6 | | | 001-099 |
| 0945 | 24 | | GK | | 3-0 | 21-51-22 | D03008 | X2 | | * | D04096 | 12 | | | 001-099 |
| 0946 | 24 | | GK | | 1-0 | 21-51-22 | D04096 | 13 | | | GD01702 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 27

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0947 | 20 | | GK | | 7-0 | 21-51-23 | D03008 | | D3 | | D41854J | 22 | | | 001-099 |
| 0948 | 22 | | GK | | 6-0 | 21-51-23 | D03006 | | C2 | | D41546J | 36 | | | 001-099 |
| 0949 | 22 | | GK | | 6-0 | 21-51-23 | D03008 | | A2 | | D41546J | 35 | | | 001-099 |
| 0950 | 22 | | GK | | 6-0 | 21-51-23 | D03008 | | B2 | | D41546J | 45 | | | 001-099 |
| 0952 | 22 | | GK | | 6-0 | 21-51-23 | D03008 | | C2 | | D41546J | 41 | | | 001-099 |
| 0953 | 24 | | GK | | 2-0 | 21-51-23 | D03034 | | X1 | | TB0180Z | 7 | BJ | | 001-099 |
| 0954 | 24 | | GK | | 6-0 | 21-51-23 | D03034 | | X2 | | D41546J | 38 | | | 001-099 |
| 0955 | 24 | | GK | | 6-0 | 21-51-23 | D03032 | | X2 | | D41546J | 37 | | | 001-099 |
| 0956 | 24 | | GK | | 2-0 | 21-51-23 | D03032 | | X1 | | TB0180Z | 7 | BJ | | 001-099 |
| 0957 | 22 | | GK | | 3-0 | 21-51-23 | D03008 | | B3 | | D03034 | A2 | | | 001-099 |
| 0958 | 24 | | GK | | 2-0 | 21-51-23 | D03034 | | A1 | | TB0180Z | 8 | BJ | | 001-099 |
| 0959 | 24 | | GK | | 2-0 | 21-51-23 | D03036 | | X1 | | TB0180Z | 7 | BJ | | 001-099 |
| 0960 | 24 | | GK | | 6-0 | 21-51-23 | D03036 | | X2 | | D41546J | 48 | | | 001-099 |
| 0961 | 22 | | GK | | 3-0 | 21-51-23 | D03008 | | C3 | | D03032 | A2 | | | 001-099 |
| 0962 | 24 | | GK | | 2-0 | 21-51-23 | D03032 | | A1 | | TB0180Z | 8 | BJ | | 001-099 |
| 0963 | 24 | | GK | | 2-0 | 21-51-23 | D03036 | | A1 | | TB0180Z | 8 | BJ | | 001-099 |
| 0964 | 22 | | GK | | 3-0 | 21-51-23 | D03008 | | A3 | | D03036 | A2 | | | 001-099 |
| 0965 | 24 | | GK | | 2-0 | 21-51-23 | D03008 | | D2 | | TB0180Z | 8 | BJ | | 001-099 |
| 0966 | 20 | | GK | | 7-0 | 21-51-23 | D03006 | | D3 | | D41854J | 26 | | | 001-099 |
| 0967 | 24 | | GK | | 7-0 | 21-51-23 | D03006 | | X2 | * | D40064J | 27 | | | 001-099 |
| 0968 | 22 | | GK | | 7-0 | 21-51-23 | D03006 | | A2 | | D40064J | 28 | | | 001-099 |
| 0969 | 22 | | GK | | 7-0 | 21-51-23 | D03006 | | B2 | | D40064J | 29 | | | 001-099 |
| 0970 | 24 | | GK | | 7-0 | 21-51-23 | D03038 | | X2 | | D40064J | 17 | | | 001-099 |
| 0972 | 24 | | GK | | 2-0 | 21-51-23 | D03038 | | X1 | | TB0180Z | 7 | BJ | | 001-099 |
| 0974 | 24 | | GK | | 7-0 | 21-51-23 | D03040 | | X2 | | D40064J | 25 | | | 001-099 |
| 0975 | 24 | | GK | | 2-0 | 21-51-23 | D03040 | | X1 | | TB0180Z | 7 | BJ | | 001-099 |
| 0976 | 24 | | GK | | 2-0 | 21-51-23 | D03042 | | X1 | | TB0180Z | 7 | BJ | | 001-099 |
| 0977 | 24 | | GK | | 7-0 | 21-51-23 | D03042 | | X2 | | D40064J | 26 | | | 001-099 |
| 0980 | 22 | | GK | | 3-0 | 21-51-23 | D03006 | | C3 | | D03038 | A2 | | | 001-099 |
| 0982 | 24 | | GK | | 2-0 | 21-51-23 | D03038 | | A1 | | TB0180Z | 8 | BJ | | 001-099 |
| 0983 | 22 | | GK | | 2-0 | 21-51-23 | D03006 | | B3 | | D03040 | A2 | | | 001-099 |
| 0984 | 24 | | GK | | 2-0 | 21-51-23 | D03040 | | A1 | | TB0180Z | 8 | BJ | | 001-099 |
| 0985 | 24 | | GK | | 2-0 | 21-51-23 | D03042 | | A1 | | TB0180Z | 8 | BJ | | 001-099 |
| 0986 | 22 | | GK | | 2-0 | 21-51-23 | D03006 | | A3 | | D03042 | A2 | | | 001-099 |
| 0987 | 24 | | GK | | 2-0 | 21-51-23 | D03006 | | D2 | | TB0180Z | 7 | BJ | | 001-099 |
| 0988 | 24 | | GK | | 7-0 | 21-51-24 | TB0180Z | 8 | BJ | | D40064J | 36 | | | 001-099 |
| 0989 | 24 | | GK | | 7-0 | 21-51-24 | D04060 | 3 | | | D40064J | 45 | | | 001-099 |
| 0990 | 24 | | GK | | 3-0 | 21-51-24 | D04060 | 7 | | | TB0180Z | 7 | BJ | | 001-099 |
| 0991 | 24 | | GK | | 7-0 | 21-51-25 | D04096 | 7 | | | D40064J | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 28

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 0992 | 24 | | GK | | 7-0 | 21-51-25 | D04096 | | 8 | | D40064J | 19 | | | 001-099 |
| 0993 | 24 | | GK | | 7-0 | 21-51-25 | D04096 | | 11 | | D40064J | 20 | | | 001-099 |
| 0994 | 24 | | GK | | 7-0 | 21-51-25 | D04096 | | 10 | | D40064J | 21 | | | 001-099 |
| 0995 | 24 | | GK | | 7-0 | 21-61-11 | D02548 | | B2 | | D41546J | 46 | | | ALL |
| 0996 | 24 | | GK | | 7-0 | 21-61-21 | D02562 | | B2 | | D41546J | 52 | | | ALL |
| 0997 | 24 | | GK | | 7-0 | 21-61-31 | D02576 | | B2 | | D41546J | 54 | | | ALL |
| 1054 | 22 | | GK | | 9-0 | 33-21-51 | D41408J | | 41 | | D07080 | C3 | | | ALL |
| 1111 | 18 | | GE | DM | 5-0 | 78-34-61 | D41478J | | 7 | 18 | TB0180A | C006 | 2 | | 001-002, 115-199 |
| 1111 | 18 | | GE | DM | 9-0 | 78-34-61 | D41478J | | 7 | 18 | TB0180A | C006 | 2 | | 003-099 |
| 1111Z | | | | DM | 0-0 | 78-34-61 | D41478J | | | | TB0180A | | | AJ | ALL |
| 1112 | 18 | | GE | DN | 5-0 | 78-34-61 | D07778 | | A2 | | TB0180A | C006 | 2 | | 001-002 |
| 1112 | 18 | | GE | DN | 9-0 | 78-34-61 | D07778 | | A2 | | TB0180A | C006 | 2 | | 003-099 |
| 1112 | 18 | | GE | DN | 4-0 | 78-34-61 | D07778 | | A2 | | TB0180A | C006 | 2 | | 115-199 |
| 1112Z | | | | DN | 0-0 | 78-34-61 | D07778 | | DED | | TB0180A | | | AJ | ALL |
| 1113 | 20 | | GE | DP | 5-0 | 78-34-61 | D07778 | | A1 | | D01864 | 8 | | | 001-002 |
| 1113 | 20 | | GE | DP | 5-0 | 78-34-61 | D01864 | | 8 | | D07778 | A1 | | | 003-099 |
| 1113 | 20 | | GE | DP | 4-0 | 78-34-61 | D07778 | | A1 | | D01864 | 8 | | | 115-199 |
| 1113Z | | | | DP | 0-0 | 78-34-61 | D07778 | | | AE | D01864 | DED | | | 001-002, 115-199 |
| 1113Z | | | | DP | 0-0 | 78-34-61 | D01864 | | DED | | D07778 | | | AE | 003-099 |
| 1114 | 20 | | GE | DR | 5-0 | 78-34-61 | D07778 | | A3 | | GD01706 | ST.. | 2 | | 001-002 |
| 1114 | 20 | | GE | DR | 5-0 | 78-34-61 | D07778 | | A3 | | GD03447 | ST.. | 2 | | 003-099 |
| 1114 | 20 | | GE | DR | 4-0 | 78-34-61 | D07778 | | A3 | | GD01706 | ST.. | 2 | | 115-199 |
| 1114Z | | | | DR | 0-0 | 78-34-61 | D07778 | | | AE | GD01706 | ST.. | 2 | | 001-002, 115-199 |
| 1114Z | | | | DR | 0-0 | 78-34-61 | D07778 | | | AE | GD03447 | ST.. | 2 | | 003-099 |
| 1115 | 20 | | GE | DS | 5-0 | 78-34-61 | D07778 | | X1 | | D42010J | 6 | | | 001-002 |
| 1115 | 20 | | GE | DS | 9-0 | 78-34-61 | D42010J | | 6 | | D07778 | X1 | | | 003-099 |
| 1115 | 20 | | GE | DS | 4-0 | 78-34-61 | D07778 | | X1 | | D42010J | 6 | | | 115-199 |
| 1115Z | | | | DS | 0-0 | 78-34-61 | D07778 | | | AE | D42010J | DED | | | 001-002, 115-199 |
| 1115Z | | | | DS | 0-0 | 78-34-61 | D42010J | | 40 | | D07778 | | | AE | 003-099 |
| 1120 | 18 | | GE | DL | 5-0 | 78-34-61 | D41478J | | 8 | 18 | GD03701 | DC.. | 2 | | 001-002 |
| 1120 | 18 | | GE | DL | 3-0 | 78-34-61 | D41478J | | 8 | 18 | GD03701 | DC.. | 2 | | 003-099 |
| 1120 | 18 | | GE | DL | 2-0 | 78-34-61 | D41478J | | 8 | 18 | GD03701 | DC.. | 2 | | 115-199 |
| 1120Z | | | | DL | 0-0 | 78-34-61 | D41478J | | | AG | GD03701 | DC.. | 2 | | ALL |
| 1148 | 22 | | GA | | 5-0 | 34-22-28 | D41909J | | 10 | | TB0179A | C015 | 2 | | 002 |
| 2001B | 22 | | GL | AA | 5-0 | 23-31-21 | D41739J | | 28 | | D40410J | 13 | | | ALL |
| 2001R | 22 | | GL | AA | 0-0 | 23-31-21 | D41739J | | 27 | | D40410J | 14 | | | ALL |
| 2002B | 24 | | GL | AH | 5-0 | 36-21-11 | D41856J | | 4 | | SM00020 | | WI | | 001-099 |
| 2002B | 24 | | GL | AH | 4-0 | 36-21-11 | D41856J | | 4 | | D40064J | 32 | | | 115-199 |
| 2002R | 24 | | GL | AH | 0-0 | 36-21-11 | D41856J | | 3 | | SM00019 | | WI | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 29

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 2002R | 24 | GL | AH | | 0-0 | 36-21-11 | D41856J | 3 | | | D40064J | 31 | | | 115-199 |
| 2003B | 24 | GL | AQ | | 7-0 | 21-31-21 | D00624 | 11 | | | D41856J | 48 | | | 001-099 |
| 2003B | 24 | GL | AQ | | 6-0 | 21-31-21 | D00624 | 11 | | | D41856J | 48 | | | 115-199 |
| 2003R | 24 | GL | AQ | | 0-0 | 21-31-21 | D00624 | 10 | | | D41856J | 49 | | | ALL |
| 2004B | 24 | GL | AR | | 9-0 | SPARE | D00610 | 9 | | | D41728J | CAP | Y | | 115-199 |
| 2004R | 24 | GL | AR | | 0-0 | SPARE | D00610 | 11 | | | D41728J | CAP | Y | | 115-199 |
| 2005B | 24 | GL | AU | | 7-0 | 21-51-22 | D01614 | 11 | | | D41546J | 39 | | | 001-099 |
| 2005B | 24 | GL | AU | | 5-0 | 21-51-22 | D01614 | 11 | | | D41546J | 39 | | | 115-199 |
| 2005R | 24 | GL | AU | | 0-0 | 21-51-22 | D01614 | 10 | | | D41546J | 40 | | | ALL |
| 2006B | 24 | GL | BH | | 7-0 | 21-51-12 | D01614 | 1 | | | D40064J | 1 | | | 001-099 |
| 2006B | 24 | GL | BH | | 5-0 | 21-51-12 | D01614 | 1 | | | D40064J | 1 | | | 115-199 |
| 2006R | 24 | GL | BH | | 0-0 | 21-51-12 | D01614 | 2 | | | D40064J | 2 | | | ALL |
| 2007B | 24 | GL | BJ | | 6-0 | 21-61-11 | D40186J | 24 | | | D41546J | 33 | | | ALL |
| 2007R | 24 | GL | BJ | | 0-0 | 21-61-11 | D40186J | 23 | | | D41546J | 34 | | | ALL |
| 2008B | 24 | GL | BK | | 6-0 | 21-61-11 | D40594J | 28 | | | D41546J | 31 | | | ALL |
| 2008R | 24 | GL | BK | | 0-0 | 21-61-11 | D40594J | 29 | | | D41546J | 32 | | | ALL |
| 2009B | 24 | GL | BL | | 7-0 | 21-51-22 | D00636 | 9 | | | D40064J | 4 | | | 001-099 |
| 2009B | 24 | GL | BL | | 6-0 | 21-51-22 | D00636 | 9 | | | D40064J | 4 | | | 115-199 |
| 2009R | 24 | GL | BL | | 0-0 | 21-51-22 | D00636 | 11 | | | D40064J | 5 | | | ALL |
| 2010B | 24 | GL | BM | | 6-0 | 21-61-11 | D40594J | 21 | | | D41546J | 44 | | | ALL |
| 2010R | 24 | GL | BM | | 0-0 | 21-61-11 | D40594J | 22 | | | D41546J | 43 | | | ALL |
| 2011B | 24 | GL | CG | | 5-0 | 36-21-11 | SM00020 | | WI | | D40064J | 16 | | | 001-099 |
| 2011R | 24 | GL | CG | | 0-0 | 36-21-11 | SM00019 | | WI | | D40064J | 15 | | | 001-099 |
| 2012B | 24 | GL | CH | | 5-0 | 36-21-11 | SM00020 | | WI | | D40064J | 32 | | | 001-099 |
| 2012R | 24 | GL | CH | | 0-0 | 36-21-11 | SM00019 | | WI | | D40064J | 31 | | | 001-099 |
| 2013B | 24 | GL | CI | | 7-0 | 21-51-22 | SM00033 | | WI | | D40064J | 10 | | | 001-099 |
| 2013R | 24 | GL | CI | | 0-0 | 21-51-22 | D04096 | 5 | | | D40064J | 59 | | | 001-099 |
| 2014B | 24 | GL | CJ | | 7-0 | 21-51-22 | SM00033 | | WI | | D40064J | 24 | | | 001-099 |
| 2014R | 24 | GL | CJ | | 0-0 | 21-51-22 | D04096 | 4 | | | D40064J | 47 | | | 001-099 |
| 2015B | 24 | GL | CK | | 7-0 | 21-51-24 | D04060 | 5 | | | D40064J | 37 | | | 001-099 |
| 2015R | 24 | GL | CK | | 0-0 | 21-51-24 | D04060 | 1 | | | D40064J | 41 | | | 001-099 |
| 2016B | 24 | GL | CL | | 7-0 | 21-51-24 | D04060 | 8 | | | D40064J | 42 | | | 001-099 |
| 2016R | 24 | GL | CL | | 0-0 | 21-51-24 | D04060 | 4 | | | D40064J | 43 | | | 001-099 |
| 2017B | 24 | GL | CM | | 7-0 | 21-51-24 | D04060 | 2 | | | D40064J | 50 | | | 001-099 |
| 2017R | 24 | GL | CM | | 0-0 | 21-51-24 | D04060 | 6 | | | D40064J | 49 | | | 001-099 |
| 2500B | 22 | X2 | CD | | 7-0 | 34-61-26 | D02277 | 1 | | | D43017J | 4 | | | 115-199 |
| 2500R | 22 | X2 | CD | | 0-0 | 34-61-26 | D02277 | 5 | | | D43017J | 3 | | | 115-199 |
| 2500Z | | | CD | | 0-0 | 34-61-26 | GD01715 | ST.. | 2 | | D43017J | 5 | | | 115-199 |
| 2501B | 22 | X2 | CE | | 7-0 | 34-61-26 | D02277 | 6 | | | D43017J | 7 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 30

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 286N1270 INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | | | | |
| 2501R | 22 | | X2 | CE | 0-0 | 34-61-26 | D02277 | | 2 | | D43017J | | 6 | | 115-199 |
| 2501Z | | | | CE | 0-0 | 34-61-26 | GD01715 | ST.. | 2 | | D43017J | | 8 | | 115-199 |
| 2502B | 22 | | X2 | CF | 7-0 | 34-61-26 | D02277 | | 8 | | D43017J | | 10 | | 115-199 |
| 2502R | 22 | | X2 | CF | 0-0 | 34-61-26 | D02277 | | 4 | | D43017J | | 9 | | 115-199 |
| 2502Z | | | | CF | 0-0 | 34-61-26 | GD01715 | ST.. | 2 | | D43017J | | 11 | | 115-199 |
| 2503B | 22 | | X2 | BX | 7-0 | 34-61-26 | D02281 | | 1 | | D43017J | | 13 | | 115-199 |
| 2503R | 22 | | X2 | BX | 0-0 | 34-61-26 | D02281 | | 5 | | D43017J | | 12 | | 115-199 |
| 2503Z | | | | BX | 0-0 | 34-61-26 | GD01715 | ST.. | 2 | | D43017J | | 14 | | 115-199 |
| 2504B | 22 | | X2 | BZ | 7-0 | 34-61-26 | D02281 | | 8 | | D43017J | | 16 | | 115-199 |
| 2504R | 22 | | X2 | BZ | 0-0 | 34-61-26 | D02281 | | 4 | | D43017J | | 15 | | 115-199 |
| 2504Z | | | | BZ | 0-0 | 34-61-26 | GD01715 | ST.. | 2 | | D43017J | | 17 | | 115-199 |
| 2505B | 22 | | X2 | CB | 7-0 | 34-61-26 | D02283 | | 1 | | D43017J | | 24 | | 115-199 |
| 2505R | 22 | | X2 | CB | 0-0 | 34-61-26 | D02283 | | 5 | | D43017J | | 23 | | 115-199 |
| 2505Z | | | | CB | 0-0 | 34-61-26 | GD01715 | ST.. | 2 | | D43017J | | 25 | | 115-199 |
| 2506B | 22 | | X2 | CA | 8-0 | 34-61-26 | D02281 | | 6 | | D02283 | | 8 | | 115-199 |
| 2506R | 22 | | X2 | CA | 0-0 | 34-61-26 | D02281 | | 2 | | D02283 | | 4 | | 115-199 |
| 2506Z | | | | CA | 0-0 | 34-61-26 | GD01715 | ST.. | 2 | | D02283 | DED | | | 115-199 |
| 2507B | 22 | | X2 | CC | 7-0 | 34-61-26 | D02283 | | 6 | | D43017J | | 27 | | 115-199 |
| 2507R | 22 | | X2 | CC | 0-0 | 34-61-26 | D02283 | | 2 | | D43017J | | 26 | | 115-199 |
| 2507Z | | | | CC | 0-0 | 34-61-26 | GD01715 | ST.. | 2 | | D43017J | | 28 | | 115-199 |
| 2508B | 24 | | G2 | CP | 6-0 | 31-31-42 | D01809 | | 6 | | D41739J | | 52 | | 001-099 |
| 2508R | 24 | | G2 | CP | 0-0 | 31-31-42 | D01809 | | 2 | | D41739J | | 51 | | 001-099 |
| 2508Z | | | | CP | 0-0 | 31-31-42 | D01809 | | | AA | D41739J | | 53 | | 001-099 |
| 2509B | 24 | | G2 | CQ | 6-0 | 31-31-42 | D01809 | | 8 | | D41637J | | 14 | | 001-099 |
| 2509R | 24 | | G2 | CQ | 0-0 | 31-31-42 | D01809 | | 4 | | D41637J | | 13 | | 001-099 |
| 2509Z | | | | CQ | 0-0 | 31-31-42 | D01809 | | | AA | D41637J | | 15 | | 001-099 |
| 2510B | 24 | | G2 | CS | 7-0 | 31-31-42 | D01809 | | 1 | | D41909J | | 47 | | 001-099 |
| 2510R | 24 | | G2 | CS | 0-0 | 31-31-42 | D01809 | | 5 | | D41909J | | 46 | | 001-099 |
| 2510Z | | | | CS | 0-0 | 31-31-42 | D01809 | | | AA | D41909J | | 48 | | 001-099 |
| 2513B | 22 | | GU | DE | 7-0 | 34-25-12 | D01923 | D01 | | | D41495J | | 25 | | 002 |
| 2513R | 22 | | GU | DE | 0-0 | 34-25-12 | D01923 | C01 | | | D41495J | | 24 | | 002 |
| 2513Z | | | | DE | 0-0 | 34-25-12 | GD01705 | ST.. | 2 | | D41495J | | 26 | | 002 |
| 2514B | 22 | | GU | DF | 7-0 | 34-25-12 | D01923 | D03 | | | D41495J | | 28 | | 002 |
| 2514R | 22 | | GU | DF | 0-0 | 34-25-12 | D01923 | C03 | | | D41495J | | 27 | | 002 |
| 2514Z | | | | DF | 0-0 | 34-25-12 | GD01705 | ST.. | 2 | | D41495J | | 29 | | 002 |
| 2515B | 22 | | GU | DH | 7-0 | 34-25-13 | D01923 | D02 | | | D41739J | | 25 | | 002 |
| 2515R | 22 | | GU | DH | 0-0 | 34-25-13 | D01923 | C02 | | | D41739J | | 24 | | 002 |
| 2515Z | | | | DH | 0-0 | 34-25-13 | GD01705 | ST.. | 2 | | D41739J | | 26 | | 002 |
| 3001B | 16 | | GC | AJ | 6-0 | 28-22-11 | D40912J | | 31 | | K10012 | C1 | D | * | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 31

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 3001B | 16 | GC | AJ | | 5-0 | 28-22-11 | D40912J | | 31 | | K10012 | C1 | D | * | 115-199 |
| 3001R | 16 | GC | AJ | | 0-0 | 28-22-11 | D40912J | | 32 | | K10012 | A1 | D | | ALL |
| 3001Y | 16 | GC | AJ | | 0-0 | 28-22-11 | D40912J | | 33 | | K10012 | B1 | D | | ALL |
| 3003B | 18 | GC | AL | | 6-0 | 28-22-11 | D40912J | | 36 | | K00189 | C1 | D | * | 001-099 |
| 3003B | 18 | GC | AL | | 5-0 | 28-22-11 | D40912J | | 36 | | K00189 | C1 | D | * | 115-199 |
| 3003R | 18 | GC | AL | | 0-0 | 28-22-11 | D40912J | | 34 | | K00189 | A1 | D | | ALL |
| 3003Y | 18 | GC | AL | | 0-0 | 28-22-11 | D40912J | | 35 | | K00189 | B1 | D | | ALL |
| 3004B | 18 | GC | AM | | 6-0 | 28-22-11 | D42062J | | 10 | | K00189 | C2 | D | | 001-099 |
| 3004B | 18 | GC | AM | | 5-0 | 28-22-11 | D42062J | | 10 | | K00189 | C2 | D | | 115-199 |
| 3004R | 18 | GC | AM | | 0-0 | 28-22-11 | D42062J | | 8 | | K00189 | A2 | D | | ALL |
| 3004Y | 18 | GC | AM | | 0-0 | 28-22-11 | D42062J | | 9 | | K00189 | B2 | D | | ALL |
| 3005B | 18 | GC | AN | | 6-0 | 28-22-11 | D40912J | | 39 | | K00188 | C1 | D | * | 001-099 |
| 3005B | 18 | GC | AN | | 5-0 | 28-22-11 | D40912J | | 39 | | K00188 | C1 | D | * | 115-199 |
| 3005R | 18 | GC | AN | | 0-0 | 28-22-11 | D40912J | | 37 | | K00188 | A1 | D | | ALL |
| 3005Y | 18 | GC | AN | | 0-0 | 28-22-11 | D40912J | | 38 | | K00188 | B1 | D | | ALL |
| 3006B | 18 | GC | AP | | 6-0 | 28-22-11 | D41732J | | 3 | | K00188 | C2 | D | | ALL |
| 3006R | 18 | GC | AP | | 0-0 | 28-22-11 | D41732J | | 1 | | K00188 | A2 | D | | ALL |
| 3006Y | 18 | GC | AP | | 0-0 | 28-22-11 | D41732J | | 2 | | K00188 | B2 | D | | ALL |
| 3007B | 24 | GM | AS | | 5-0 | 21-61-11 | D41856J | | 11 | | D41546J | 7 | | | ALL |
| 3007R | 24 | GM | AS | | 0-0 | 21-61-11 | D41856J | | 10 | | D41546J | 8 | | | ALL |
| 3007Y | 24 | GM | AS | | 0-0 | 21-61-11 | D41856J | | 12 | | D41546J | 6 | | | ALL |
| 3008B | 24 | GM | AT | | 5-0 | 21-61-21 | D41856J | | 18 | | D41546J | 19 | | | ALL |
| 3008R | 24 | GM | AT | | 0-0 | 21-61-21 | D41856J | | 17 | | D41546J | 20 | | | ALL |
| 3008Y | 24 | GM | AT | | 0-0 | 21-61-21 | D41856J | | 19 | | D41546J | 18 | | | ALL |
| 3009B | 24 | GM | AV | | 5-0 | 21-61-31 | D41856J | | 24 | | D41546J | 22 | | | ALL |
| 3009R | 24 | GM | AV | | 0-0 | 21-61-31 | D41856J | | 23 | | D41546J | 23 | | | ALL |
| 3009Y | 24 | GM | AV | | 0-0 | 21-61-31 | D41856J | | 25 | | D41546J | 21 | | | ALL |
| 3010B | 24 | GM | CR | | 7-0 | 28-41-14 | D00632 | | 9 | | D41728J | 40 | | | 001-099 |
| 3010B | 24 | GM | CR | | 7-0 | 28-41-14 | D00632 | | 9 | | D41728J | 3 | | | 115-199 |
| 3010R | 24 | GM | CR | | 0-0 | 28-41-14 | D00632 | | 11 | | D41728J | 42 | | | 001-099 |
| 3010R | 24 | GM | CR | | 0-0 | 28-41-14 | D00632 | | 11 | | D41728J | 4 | | | 115-199 |
| 3010Y | 24 | GM | CR | | 0-0 | 28-41-14 | D00632 | | 10 | | D41728J | 41 | | | 001-099 |
| 3010Y | 24 | GM | CR | | 0-0 | 28-41-14 | D00632 | | 10 | | D41728J | 5 | | | 115-199 |
| 3501B | 16 | VH | FA | | 4-0 | 28-22-11 | K10012 | | C2 | D | K10874 | C2 | D | | ALL |
| 3501R | 16 | VH | FA | | 0-0 | 28-22-11 | K10012 | | A2 | D | K10874 | A2 | D | | ALL |
| 3501Y | 16 | VH | FA | | 0-0 | 28-22-11 | K10012 | | B2 | D | K10874 | B2 | D | | ALL |
| 3501Z | | | FA | | 0-0 | 28-22-11 | K10012 | DED | | | K10874 | DED | | | ALL |
| 3502B | 16 | VH | FB | | 5-0 | 28-22-11 | K10874 | | C1 | D | D42062J | 4 | | | ALL |
| 3502R | 16 | VH | FB | | 0-0 | 28-22-11 | K10874 | | A1 | D | D42062J | 2 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 32

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1270
Page 33
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5006Z | | | | AG | 0-0 | 31-31-41 | D41739J | 11 | | | GD01700 | ST.. | 2 | | 001-099 |
| 5006Z | | | | AG | 0-0 | 31-31-21 | D41739J | 11 | | | GD01701 | ST.. | 2 | | 115-199 |
| 5013B | 22 | G2 | | BC | 8-0 | 32-42-11 | D04268 | 6 | | | D41748J | 23 | | | 001-099 |
| 5013B | 22 | G2 | | BC | 8-0 | 32-42-11 | D04268 | 6 | | | SM00041 | | WI | | 115-199 |
| 5013R | 22 | G2 | | BC | 0-0 | 32-42-11 | D04268 | 2 | | | D41748J | 22 | | | 001-099 |
| 5013R | 22 | G2 | | BC | 0-0 | 32-42-11 | D04268 | 2 | | | SM00042 | | WI | | 115-199 |
| 5013Z | | | | BC | 0-0 | 32-42-11 | GD01701 | ST.. | 2 | | D41748J | 24 | | | 001-099 |
| 5013Z | | | | BC | 0-0 | 32-42-11 | GD01701 | ST.. | 2 | | SM00043 | | WI | | 115-199 |
| 5014B | 22 | G2 | | BD | 7-0 | 32-42-11 | D04268 | 8 | | | D41487J | 29 | | | 001-099 |
| 5014B | 22 | G2 | | BD | 6-0 | 32-42-11 | D04268 | 8 | | | D41487J | 29 | | | 115-199 |
| 5014R | 22 | G2 | | BD | 0-0 | 32-42-11 | D04268 | 4 | | | D41487J | 30 | | | ALL |
| 5014Z | | | | BD | 0-0 | 32-42-11 | GD01701 | ST.. | 2 | | D41487J | 31 | | | ALL |
| 5015B | 22 | G2 | | BE | 4-0 | 32-42-11 | D04268 | 1 | | | TB0170Y | C009 | BJ | | 001-099 |
| 5015B | 22 | G2 | | BE | 4-0 | 32-42-11 | D04268 | 1 | | | TB0170Y | C015 | BJ | | 115-199 |
| 5015R | 22 | G2 | | BE | 0-0 | 32-42-11 | D04268 | 5 | | | TB0170Y | A008 | BJ | | 001-099 |
| 5015R | 22 | G2 | | BE | 0-0 | 32-42-11 | D04268 | 5 | | | TB0170Y | C016 | BJ | | 115-199 |
| 5015Z | | | | BE | 0-0 | 32-42-11 | GD01701 | ST.. | 2 | | GD01700 | ST.. | 2 | | 001-099 |
| 5015Z | | | | BE | 0-0 | 32-42-11 | GD01701 | ST.. | 2 | | SM00001 | | WI | | 115-199 |
| 5016B | 22 | G2 | | BF | 8-0 | 32-42-11 | D41860J | 8 | | | TB0170Y | C009 | BJ | | 001-099 |
| 5016B | 22 | G2 | | BF | 9-0 | 32-42-11 | D41860J | 8 | | | TB0170Y | C015 | BJ | | 115-199 |
| 5016R | 22 | G2 | | BF | 0-0 | 32-42-11 | D41860J | 9 | | | TB0170Y | A008 | BJ | | 001-099 |
| 5016R | 22 | G2 | | BF | 0-0 | 32-42-11 | D41860J | 9 | | | TB0170Y | C016 | BJ | | 115-199 |
| 5016Z | | | | BF | 0-0 | 32-42-11 | D41860J | 10 | | | GD01701 | ST.. | 2 | | 001-099 |
| 5016Z | | | | BF | 0-0 | 32-42-11 | D41860J | 10 | | | SM00001 | | WI | | 115-199 |
| 5017B | 22 | G2 | | BG | 7-0 | 32-42-11 | D41495J | 8 | | | TB0170Y | C009 | BJ | | 001-099 |
| 5017B | 22 | G2 | | BG | 6-0 | 32-42-11 | D41495J | 8 | | | TB0170Y | C015 | BJ | | 115-199 |
| 5017R | 22 | G2 | | BG | 0-0 | 32-42-11 | D41495J | 9 | | | TB0170Y | A008 | BJ | | 001-099 |
| 5017R | 22 | G2 | | BG | 0-0 | 32-42-11 | D41495J | 9 | | | TB0170Y | C016 | BJ | | 115-199 |
| 5017Z | | | | BG | 0-0 | 32-42-11 | D41495J | 10 | | | GD01701 | ST.. | 2 | | 001-099 |
| 5017Z | | | | BG | 0-0 | 32-42-11 | D41495J | 10 | | | SM00001 | | WI | | 115-199 |
| 5019B | 24 | G2 | | AO | 9-0 | 34-61-25 | D02526 | B2 | | | D41909J | 36 | | | ALL |
| 5019R | 24 | G2 | | AO | 0-0 | 34-61-25 | D02526 | A2 | | | D41909J | 37 | | | ALL |
| 5019Z | | | | AO | 0-0 | 34-61-25 | GD01704 | ST.. | 2 | | D41909J | 38 | | | 001-099 |
| 5019Z | | | | AO | 0-0 | 34-61-25 | GD01702 | ST.. | 2 | | D41909J | 38 | | | 115-199 |
| 5020B | 24 | G2 | | BI | 9-0 | 34-61-25 | D02526 | B1 | | | D41909J | 40 | | | ALL |
| 5020R | 24 | G2 | | BI | 0-0 | 34-61-25 | D02526 | A1 | | | D41909J | 39 | | | ALL |
| 5020Z | | | | BI | 0-0 | 34-61-25 | GD01704 | ST.. | 2 | | D41909J | 41 | | | 001-099 |
| 5020Z | | | | BI | 0-0 | 34-61-25 | GD01702 | ST.. | 2 | | D41909J | 41 | | | 115-199 |
| 5021B | 24 | G2 | | AI | 9-0 | 34-61-25 | D02526 | B3 | | | D41909J | 34 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 34

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5021R | 24 | G2 | AI | | 0-0 | 34-61-25 | D02526 | A3 | | | D41909J | 33 | | | ALL |
| 5021Z | | | AI | | 0-0 | 34-61-25 | GD01704 | ST.. | 2 | | D41909J | 35 | | | 001-099 |
| 5021Z | | | AI | | 0-0 | 34-61-25 | GD01702 | ST.. | 2 | | D41909J | 35 | | | 115-199 |
| 5022B | 22 | G2 | BB | | 4-0 | 32-42-11 | D40064J | 9 | | | SM00041 | | WI | | 115-199 |
| 5022R | 22 | G2 | BB | | 0-0 | 32-42-11 | D40064J | 8 | | | SM00042 | | WI | | 115-199 |
| 5022Z | | | BB | | 0-0 | 32-42-11 | D40064J | 10 | | | SM00043 | | WI | | 115-199 |
| 5023B | 24 | G2 | CN | | 4-0 | 27-32-21 | D41909J | 51 | | | SM00041 | | WI | | 115-199 |
| 5023R | 24 | G2 | CN | | 0-0 | 27-32-21 | D41909J | 50 | | | SM00042 | | WI | | 115-199 |
| 5023Z | | | CN | | 0-0 | 27-32-21 | D41909J | 52 | | | SM00043 | | WI | | 115-199 |
| 5030B | 22 | GU | KA | | 6-0 | 31-31-41 | D04015 | 1 | | | SM00302 | | WI | | 010-099 |
| 5030R | 22 | GU | KA | | 0-0 | 31-31-41 | D04015 | 5 | | | SM00301 | | WI | | 010-099 |
| 5030Z | | | KA | | 0-0 | 31-31-41 | GD01711 | ST.. | 2 | | SM00303 | | WI | | 010-099 |
| 5031B | 22 | GU | KB | | 8-0 | 31-31-41 | D04015 | 6 | | | D41909J | 50 | | | 010-099 |
| 5031R | 22 | GU | KB | | 0-0 | 31-31-41 | D04015 | 2 | | | D41909J | 49 | | | 010-099 |
| 5031Z | | | KB | | 0-0 | 31-31-41 | D41909J | 51 | | | GD01711 | ST.. | 2 | | 010-099 |
| 5032B | 22 | GU | KC | | 8-0 | 31-31-41 | D04015 | 8 | | | D41487J | 17 | | | 010-099 |
| 5032R | 22 | GU | KC | | 0-0 | 31-31-41 | D04015 | 4 | | | D41487J | 15 | | | 010-099 |
| 5032Z | | | KC | | 0-0 | 31-31-41 | D41487J | 18 | | | GD01711 | ST.. | 2 | | 010-099 |
| 5033B | 22 | GU | AR | | 6-0 | 31-31-41 | D41495J | 3 | | | SM00302 | | WI | | 010-099 |
| 5033R | 22 | GU | AR | | 0-0 | 31-31-41 | D41495J | 2 | | | SM00301 | | WI | | 010-099 |
| 5033Z | | | AR | | 0-0 | 31-31-41 | D41495J | 1 | | | SM00303 | | WI | | 010-099 |
| 5500 | 24 | GK | | | 7-0 | 21-51-21 | D00628 | 8 | | | D40064J | 61 | | | 001-099 |
| 5500 | 24 | GK | | | 6-0 | 21-51-21 | D00628 | 8 | | | D40064J | 61 | | | 115-199 |
| 5501 | 24 | GK | | | 4-0 | 21-51-21 | D00628 | 7 | | | GD01702 | DC.. | 2 | | ALL |
| 5510 | 24 | GK | | | 9-0 | 21-58-12 | D00574 | 4 | | | TB0178A | A038 | 2 | | 001-099 |
| 5510 | 24 | GK | | | 8-0 | 21-58-12 | D00574 | 4 | | | TB0178A | A038 | 2 | | 115-199 |
| 5511 | 24 | GK | | | 7-0 | 21-58-12 | D41034J | 3 | | | TB0172A | C013 | 2 | | 001-099 |
| 5511 | 24 | GK | | | 8-0 | 21-58-12 | D41034J | 3 | | | TB0172A | C013 | 2 | | 115-199 |
| 5513 | 24 | GK | | | 4-0 | 21-25-11 | D05188 | 7 | | | TB0170A | C007 | 2 | * | ALL |
| 5517 | 24 | GK | | | 7-0 | 21-58-12 | D41034J | 1 | | | TB0170A | C005 | 2 | | 001-099 |
| 5517 | 24 | GK | | | 8-0 | 21-58-12 | D41034J | 1 | | | TB0170A | C005 | 2 | | 115-199 |
| 5519 | 24 | GK | | | 4-0 | 21-58-12 | D00574 | 3 | | | TB0170A | A005 | 2 | | ALL |
| 5521 | 24 | GK | | | 3-0 | 23-12-31 | D00610 | 13 | | | GD01702 | DC.. | 2 | | 001-099 |
| 5522 | 24 | GK | | | 7-0 | 23-12-31 | D41739J | 45 | | | D00610 | 1 | | | 001-099 |
| 5525 | 18 | GK | | | 9-0 | 21-58-21 | D04232 | A1 | | | TB0177F | A001 | 2 | | 001-099 |
| 5525 | 18 | GK | | | 10-0 | 21-58-21 | D04232 | A1 | | | TB0177F | A001 | 2 | | 115-199 |
| 5526 | 18 | GK | | | 9-0 | 21-58-21 | D04232 | B1 | | | TB0177F | C001 | 2 | | 001-099 |
| 5526 | 18 | GK | | | 10-0 | 21-58-21 | D04232 | B1 | | | TB0177F | C001 | 2 | | 115-199 |
| 5527 | 18 | GK | | | 9-0 | 21-58-21 | D04232 | C1 | | * | TB0177F | A002 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 35

Oct 09/2008



WIRE LIST

91-21-11

Section W1270

Page 36

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5587 | 24 | | GK | | 7-0 | 21-61-11 | D02548 | | C3 | | D41546J | | 3 | | 001-099 |
| 5587 | 24 | | GK | | 6-0 | 21-61-11 | D02548 | | C3 | | D41546J | | 3 | | 115-199 |
| 5588 | 24 | | GK | | 7-0 | 21-61-11 | D02548 | | B3 | | D41546J | | 4 | | 001-099 |
| 5588 | 24 | | GK | | 6-0 | 21-61-11 | D02548 | | B3 | | D41546J | | 4 | | 115-199 |
| 5589 | 24 | | GK | | 7-0 | 21-61-11 | D41854J | | 30 | | TB0170Z | 11 | BJ | | 001-099 |
| 5589 | 24 | | GK | | 8-0 | 21-61-11 | D41854J | | 30 | | TB0170Z | 11 | BJ | | 115-199 |
| 5590 | 24 | | GK | | 4-0 | 21-61-11 | D02548 | | A2 | | GD01704 | DC.. | 2 | | ALL |
| 5591 | 24 | | GK | | 7-0 | 21-61-11 | D02548 | | B1 | | D41546J | | 9 | | 001-099 |
| 5591 | 24 | | GK | | 6-0 | 21-61-11 | D02548 | | B1 | | D41546J | | 9 | | 115-199 |
| 5592 | 24 | | GK | | 7-0 | 21-61-11 | D02548 | | C2 | | D41546J | | 10 | | 001-099 |
| 5592 | 24 | | GK | | 6-0 | 21-61-11 | D02548 | | C2 | | D41546J | | 10 | | 115-199 |
| 5593 | 24 | | GK | | 7-0 | 21-61-11 | D02548 | | D2 | | D41546J | | 1 | | 001-099 |
| 5593 | 24 | | GK | | 6-0 | 21-61-11 | D02548 | | D2 | | D41546J | | 1 | | 115-199 |
| 5594 | 24 | | GK | | 7-0 | 21-61-11 | D41856J | | 14 | | D04196 | | 3 | | 001-099 |
| 5594 | 24 | | GK | | 8-0 | 21-61-11 | D41856J | | 14 | | D04196 | | 3 | | 115-199 |
| 5595 | 24 | | GK | | 4-0 | 21-61-11 | GD01700 | | DC.. | 2 | D04196 | | 4 | | ALL |
| 5596 | 24 | | GK | | 4-0 | 21-61-11 | GD01700 | | DC.. | 2 | D04196 | | 1 | | ALL |
| 5597 | 24 | | GK | | 4-0 | 21-61-11 | TB0170Z | | 11 | BJ | D04196 | | 7 | | ALL |
| 5598 | 24 | | GK | | 4-0 | 21-61-11 | TB0170Z | | 11 | BJ | D04344 | | 7 | | ALL |
| 5599 | 24 | | GK | | 2-0 | 21-61-11 | D04196 | | 6 | | D04344 | | 5 | | 001-099 |
| 5599 | 24 | | GK | | 4-0 | 21-61-11 | D04196 | | 6 | | D04344 | | 5 | | 115-199 |
| 5600 | 24 | | GK | | 2-0 | 21-61-11 | GD01701 | | DC.. | 2 | D04344 | | 6 | | 001-099 |
| 5600 | 24 | | GK | | 4-0 | 21-61-11 | GD01701 | | DC.. | 2 | D04344 | | 6 | | 115-199 |
| 5601 | 24 | | GK | | 4-0 | 21-61-11 | TB0170Y | | C008 | BJ | D04344 | | 2 | | 001-099 |
| 5601 | 24 | | GK | | 4-0 | 21-61-11 | TB0170Y | | C010 | BJ | D04344 | | 2 | | 115-199 |
| 5602 | 24 | | GK | | 4-0 | 21-61-11 | TB0170Y | | C008 | BJ | D04344 | | 3 | | 001-099 |
| 5602 | 24 | | GK | | 4-0 | 21-61-11 | TB0170Y | | C010 | BJ | D04344 | | 3 | | 115-199 |
| 5603 | 24 | | GK | | 7-0 | 21-61-11 | TB0170Y | | C008 | BJ | D41546J | | 5 | | 001-099 |
| 5603 | 24 | | GK | | 6-0 | 21-61-11 | TB0170Y | | C010 | BJ | D41546J | | 5 | | 115-199 |
| 5604 | 24 | | GK | | 2-0 | 21-61-21 | TB0179A | | A008 | 2 | TB0179Z | 4 | BJ | | 001-099 |
| 5604 | 24 | | GK | | 2-0 | 21-61-21 | TB0179D | | A008 | 2 | TB0179Z | 4 | BJ | | 115-199 |
| 5605 | 24 | | GK | | 7-0 | 21-61-21 | D40064J | | 14 | | TB0179Z | 4 | BJ | | 001-099 |
| 5605 | 24 | | GK | | 8-0 | 21-61-21 | D40064J | | 14 | | TB0179Z | 4 | BJ | | 115-199 |
| 5606 | 24 | | GK | | 4-0 | 21-61-21 | D02562 | | X2 | | TB0179Z | 4 | BJ | | ALL |
| 5607 | 24 | | GK | | 5-0 | 21-61-21 | D04198 | | 2 | | TB0179Z | 4 | BJ | | ALL |
| 5608 | 24 | | GK | | 5-0 | 21-61-21 | D04346 | | 1 | | TB0179Z | 4 | BJ | | ALL |
| 5609 | 24 | | GK | | 7-0 | 21-61-21 | D02562 | | B1 | | D41546J | | 11 | | 001-099 |
| 5609 | 24 | | GK | | 6-0 | 21-61-21 | D02562 | | B1 | | D41546J | | 11 | | 115-199 |
| 5610 | 24 | | GK | | 7-0 | 21-61-21 | D02562 | | C2 | | D41546J | | 12 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 37

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5610 | 24 | | GK | | 6-0 | 21-61-21 | D02562 | | C2 | | D41546J | | 12 | | 115-199 |
| 5611 | 24 | | GK | | 7-0 | 21-61-21 | D02562 | | D2 | | D41546J | | 13 | | 001-099 |
| 5611 | 24 | | GK | | 6-0 | 21-61-21 | D02562 | | D2 | | D41546J | | 13 | | 115-199 |
| 5612 | 24 | | GK | | 7-0 | 21-61-21 | D02562 | | D3 | | D41546J | | 14 | | 001-099 |
| 5612 | 24 | | GK | | 6-0 | 21-61-21 | D02562 | | D3 | | D41546J | | 14 | | 115-199 |
| 5613 | 24 | | GK | | 7-0 | 21-61-21 | D02562 | | C3 | | D41546J | | 15 | | 001-099 |
| 5613 | 24 | | GK | | 6-0 | 21-61-21 | D02562 | | C3 | | D41546J | | 15 | | 115-199 |
| 5614 | 24 | | GK | | 7-0 | 21-61-21 | D02562 | | B3 | | D41546J | | 16 | | 001-099 |
| 5614 | 24 | | GK | | 6-0 | 21-61-21 | D02562 | | B3 | | D41546J | | 16 | | 115-199 |
| 5615 | 24 | | GK | | 7-0 | 21-61-21 | D02562 | | X1 | | D40718J | | 5 | | 001-099 |
| 5615 | 24 | | GK | | 8-0 | 21-61-21 | D02562 | | X1 | | D40718J | | 5 | | 115-199 |
| 5616 | 24 | | GK | | 6-0 | 21-61-21 | D02562 | | A1 | | SM00034 | | | WI | 001-099 |
| 5616 | 24 | | GK | | 4-0 | 21-61-21 | D02562 | | A1 | | TB0179Y | C005 | BJ | | 115-199 |
| 5617 | 24 | | GK | | 3-0 | 21-61-21 | D41856J | | 15 | | SM00034 | | | WI | 001-099 |
| 5617 | 24 | | GK | | 6-0 | 21-61-21 | D41856J | | 15 | | TB0179Y | C005 | BJ | | 115-199 |
| 5618 | 24 | | GK | | 3-0 | 21-61-21 | D41856J | | 20 | | SM00034 | | | WI | 001-099 |
| 5618 | 24 | | GK | | 6-0 | 21-61-21 | D41856J | | 20 | | TB0179Y | C005 | BJ | | 115-199 |
| 5619 | 24 | | GK | | 7-0 | 21-61-21 | D40718J | | 17 | | D41546J | | 53 | | 001-099 |
| 5619 | 24 | | GK | | 6-0 | 21-61-21 | D40718J | | 17 | | D41546J | | 53 | | 115-199 |
| 5620 | 24 | | GK | | 4-0 | 21-61-21 | D04198 | | 7 | | TB0170Z | | 11 | BJ | 001-099 |
| 5620 | 24 | | GK | | 5-0 | 21-61-21 | D04198 | | 7 | | TB0170Z | | 11 | BJ | 115-199 |
| 5621 | 24 | | GK | | 4-0 | 21-61-21 | D04346 | | 7 | | TB0170Z | | 11 | BJ | ALL |
| 5622 | 24 | | GK | | 2-0 | 21-61-21 | D04198 | | 6 | | D04346 | | 5 | | 001-099 |
| 5622 | 24 | | GK | | 4-0 | 21-61-21 | D04198 | | 6 | | D04346 | | 5 | | 115-199 |
| 5623 | 24 | | GK | | 7-0 | 21-61-21 | D04198 | | 3 | | D41856J | | 16 | | 001-099 |
| 5623 | 24 | | GK | | 6-0 | 21-61-21 | D04198 | | 3 | | D41856J | | 16 | | 115-199 |
| 5624 | 24 | | GK | | 4-0 | 21-61-21 | D04198 | | 4 | | GD01700 | DC.. | 2 | | ALL |
| 5625 | 24 | | GK | | 4-0 | 21-61-21 | D04198 | | 1 | | GD01700 | DC.. | 2 | | ALL |
| 5626 | 24 | | GK | | 2-0 | 21-61-21 | D04346 | | 6 | | GD01701 | DC.. | 2 | | 001-099 |
| 5626 | 24 | | GK | | 4-0 | 21-61-21 | D04346 | | 6 | | GD01701 | DC.. | 2 | | 115-199 |
| 5627 | 24 | | GK | | 4-0 | 21-61-21 | D04346 | | 2 | | TB0170Y | A013 | BJ | | ALL |
| 5628 | 24 | | GK | | 4-0 | 21-61-21 | D04346 | | 3 | | TB0170Y | A013 | BJ | | ALL |
| 5629 | 24 | | GK | | 7-0 | 21-61-21 | D41546J | | 17 | | TB0170Y | A013 | BJ | | 001-099 |
| 5629 | 24 | | GK | | 6-0 | 21-61-21 | D41546J | | 17 | | TB0170Y | A013 | BJ | | 115-199 |
| 5630 | 24 | | GK | | 4-0 | 21-61-21 | D02562 | | A2 | | GD01704 | DC.. | 2 | | ALL |
| 5631 | 24 | | GK | | 7-0 | 21-61-31 | D02576 | | X1 | | D40718J | | 6 | | 001-099 |
| 5631 | 24 | | GK | | 8-0 | 21-61-31 | D02576 | | X1 | | D40718J | | 6 | | 115-199 |
| 5632 | 24 | | GK | | 7-0 | 21-61-31 | D41546J | | 55 | | D40718J | | 33 | | 001-099 |
| 5632 | 24 | | GK | | 6-0 | 21-61-31 | D41546J | | 55 | | D40718J | | 33 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 38

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5633 | 24 | | GK | | 8-0 | 21-61-31 | D02576 | | A1 | | TB0178Y | A006 | BJ | | 001-099 |
| 5633 | 24 | | GK | | 4-0 | 21-61-31 | D02576 | | A1 | | TB0179Y | A006 | BJ | | 115-199 |
| 5634 | 24 | | GK | | 5-0 | 21-61-31 | D41856J | | 41 | | TB0178Y | A006 | BJ | | 001-099 |
| 5634 | 24 | | GK | | 7-0 | 21-61-31 | D41856J | | 41 | | TB0179Y | A006 | BJ | | 115-199 |
| 5635 | 24 | | GK | | 5-0 | 21-61-31 | D41856J | | 22 | | TB0178Y | A006 | BJ | | 001-099 |
| 5635 | 24 | | GK | | 7-0 | 21-61-31 | D41856J | | 22 | | TB0179Y | A006 | BJ | | 115-199 |
| 5636 | 24 | | GK | | 7-0 | 21-61-31 | D02576 | | B3 | | D41546J | 30 | | | 001-099 |
| 5636 | 24 | | GK | | 6-0 | 21-61-31 | D02576 | | B3 | | D41546J | 30 | | | 115-199 |
| 5637 | 24 | | GK | | 7-0 | 21-61-31 | D02576 | | C3 | | D41546J | 29 | | | 001-099 |
| 5637 | 24 | | GK | | 6-0 | 21-61-31 | D02576 | | C3 | | D41546J | 29 | | | 115-199 |
| 5638 | 24 | | GK | | 7-0 | 21-61-31 | D02576 | | D3 | | D41546J | 28 | | | 001-099 |
| 5638 | 24 | | GK | | 6-0 | 21-61-31 | D02576 | | D3 | | D41546J | 28 | | | 115-199 |
| 5639 | 24 | | GK | | 4-0 | 21-61-31 | D02576 | | X2 | | TB0179A | A009 | 2 | | 001-099 |
| 5639 | 24 | | GK | | 9-0 | 21-61-31 | D02576 | | X2 | | TB0179D | A009 | 2 | | 115-199 |
| 5640 | 24 | | GK | | 4-0 | 21-61-31 | TB0170Y | | A012 | BJ | TB0179A | A009 | 2 | | 001-099 |
| 5640 | 24 | | GK | | 9-0 | 21-61-31 | TB0170Y | | A014 | BJ | TB0179D | A009 | 2 | | 115-199 |
| 5641 | 24 | | GK | | 7-0 | 21-61-31 | TB0170Y | | A012 | BJ | D40064J | 13 | | | 001-099 |
| 5641 | 24 | | GK | | 6-0 | 21-61-31 | TB0170Y | | A014 | BJ | D40064J | 13 | | | 115-199 |
| 5642 | 24 | | GK | | 4-0 | 21-61-31 | TB0170Y | | A012 | BJ | D04200 | 2 | | | 001-099 |
| 5642 | 24 | | GK | | 4-0 | 21-61-31 | TB0170Y | | A014 | BJ | D04200 | 2 | | | 115-199 |
| 5643 | 24 | | GK | | 4-0 | 21-61-31 | TB0170Y | | A012 | BJ | D04348 | 1 | | | 001-099 |
| 5643 | 24 | | GK | | 4-0 | 21-61-31 | TB0170Y | | A014 | BJ | D04348 | 1 | | | 115-199 |
| 5644 | 24 | | GK | | 4-0 | 21-61-31 | D02576 | | A2 | | GD01704 | DC.. | 2 | | ALL |
| 5645 | 24 | | GK | | 7-0 | 21-61-31 | D02576 | | C2 | | D41546J | 25 | | | 001-099 |
| 5645 | 24 | | GK | | 6-0 | 21-61-31 | D02576 | | C2 | | D41546J | 25 | | | 115-199 |
| 5646 | 24 | | GK | | 7-0 | 21-61-31 | D02576 | | D2 | | D41546J | 26 | | | 001-099 |
| 5646 | 24 | | GK | | 6-0 | 21-61-31 | D02576 | | D2 | | D41546J | 26 | | | 115-199 |
| 5647 | 24 | | GK | | 4-0 | 21-61-31 | D04200 | | 7 | | TB0170Z | 11 | BJ | | ALL |
| 5648 | 24 | | GK | | 4-0 | 21-61-31 | D04348 | | 7 | | TB0170Z | 11 | BJ | | ALL |
| 5649 | 24 | | GK | | 4-0 | 21-61-31 | D04348 | | 5 | | D04200 | 6 | | | ALL |
| 5650 | 24 | | GK | | 7-0 | 21-61-31 | D41856J | | 21 | | D04200 | 3 | | | 001-099 |
| 5650 | 24 | | GK | | 6-0 | 21-61-31 | D41856J | | 21 | | D04200 | 3 | | | 115-199 |
| 5651 | 24 | | GK | | 4-0 | 21-61-31 | GD01700 | | DC.. | 2 | D04200 | 4 | | | ALL |
| 5652 | 24 | | GK | | 4-0 | 21-61-31 | GD01700 | | DC.. | 2 | D04200 | 1 | | | ALL |
| 5653 | 24 | | GK | | 4-0 | 21-61-31 | D04348 | | 2 | | TB0170Y | C013 | BJ | | ALL |
| 5654 | 24 | | GK | | 4-0 | 21-61-31 | D04348 | | 3 | | TB0170Y | C013 | BJ | | ALL |
| 5655 | 24 | | GK | | 7-0 | 21-61-31 | TB0170Y | | C013 | BJ | D41546J | 27 | | | 001-099 |
| 5655 | 24 | | GK | | 6-0 | 21-61-31 | TB0170Y | | C013 | BJ | D41546J | 27 | | | 115-199 |
| 5656 | 24 | | GK | | 7-0 | 21-61-51 | D41854J | | 10 | | TB0179A | C009 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 39

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5656 | 24 | | GK | | 7-0 | 21-61-51 | D41854J | | 10 | | TB0179D | C009 | 2 | | 115-199 |
| 5666 | 24 | | GK | | 4-0 | 21-25-11 | D05188 | | 3 | | TB0170A | A007 | 2 | | ALL |
| 5668 | 24 | | GK | | 7-0 | 21-25-11 | D05188 | | 4 | | D41030J | 21 | | | ALL |
| 5675 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 2 | | GD01702 | DC.. | 2 | | 001-099 |
| 5675 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 2 | | GD01700 | DC.. | 2 | | 115-199 |
| 5676 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 4 | | GD01702 | DC.. | 2 | | 001-099 |
| 5676 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 4 | | GD01700 | DC.. | 2 | | 115-199 |
| 5677 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 8 | | GD01702 | DC.. | 2 | | 001-099 |
| 5677 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 8 | | GD01700 | DC.. | 2 | | 115-199 |
| 5678 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 10 | | GD01702 | DC.. | 2 | | 001-099 |
| 5678 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 10 | | GD01700 | DC.. | 2 | | 115-199 |
| 5679 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 1 | | TB0170Y | C012 | BJ | | 001-099 |
| 5679 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 1 | | TB0170Y | C014 | BJ | | 115-199 |
| 5680 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 5 | | TB0170Y | C012 | BJ | | 001-099 |
| 5680 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 5 | | TB0170Y | C014 | BJ | | 115-199 |
| 5681 | 22 | | GK | | 9-0 | 22-14-31 | D41909J | | 23 | | TB0170Y | C012 | BJ | | 001-099 |
| 5681 | 22 | | GK | | 9-0 | 22-14-31 | D41909J | | 23 | | TB0170Y | C014 | BJ | | 115-199 |
| 5682 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 7 | | TB0170Y | C003 | BJ | | 001-099 |
| 5682 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 7 | | TB0170Y | A015 | BJ | | 115-199 |
| 5683 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 11 | | TB0170Y | C003 | BJ | | 001-099 |
| 5683 | 22 | | GK | | 4-0 | 22-14-31 | D00614 | | 11 | | TB0170Y | A015 | BJ | | 115-199 |
| 5684 | 22 | | GK | | 9-0 | 22-14-31 | D41909J | | 19 | | TB0170Y | C003 | BJ | | 001-099 |
| 5684 | 22 | | GK | | 9-0 | 22-14-31 | D41909J | | 19 | | TB0170Y | A015 | BJ | | 115-199 |
| 5691 | 24 | | GK | | 9-0 | 24-22-22 | D00632 | | 5 | | D41909J | 18 | | | ALL |
| 5692 | 24 | | GK | | 7-0 | 24-22-22 | D00632 | | 3 | | D41032J | 34 | | | 001-099 |
| 5692 | 24 | | GK | | 9-0 | 24-22-22 | D00632 | | 3 | | D41032J | 34 | | | 115-199 |
| 5695 | 24 | | GK | | 10-0 | 24-51-71 | D00632 | | 1 | | TB0173Y | C001 | BJ | | 001-099 |
| 5695 | 24 | | GK | | 9-0 | 24-51-71 | D00632 | | 1 | | TB0178Y | C003 | BJ | | 115-199 |
| 5696 | 24 | | GK | | 9-0 | 24-51-71 | D00632 | | 2 | | TB0178X | B005 | BJ | | 115-199 |
| 5701 | 22 | | GK | | 7-0 | 27-09-12 | D01872 | | 11 | | D41495J | 15 | | | 001-099 |
| 5701 | 22 | | GK | | 6-0 | 27-09-12 | D01872 | | 11 | | D41495J | 15 | | | 115-199 |
| 5702 | 22 | | GK | | 3-0 | 27-09-12 | D01872 | | 10 | | GD01703 | DC.. | 2 | | 001-099 |
| 5702 | 22 | | GK | | 4-0 | 27-09-12 | D01872 | | 10 | | GD01705 | DC.. | 2 | | 115-199 |
| 5703 | 22 | | GK | | 8-0 | 27-23-11 | D00616 | | C2 | | D42176J | 24 | | | 001-099 |
| 5703 | 22 | | GK | | 6-0 | 27-23-11 | D00616 | | C2 | | D41616J | 24 | | | 115-199 |
| 5704 | 22 | | GK | | 6-0 | 27-23-11 | D00616 | | C3 | | D41616J | 25 | | | 115-199 |
| 5705 | 22 | | GK | | 7-0 | 27-23-11 | D00616 | | C1 | | D41616J | 26 | | | 001-099 |
| 5705 | 22 | | GK | | 6-0 | 27-23-11 | D00616 | | C1 | | D41616J | 26 | | | 115-199 |
| 5706 | 24 | | GK | | 4-0 | 27-32-21 | D01872 | | 13 | | TB0171Y | C002 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 40

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5706 | 24 | | GK | | 4-0 | 27-32-21 | D01872 | | 13 | | TB0170Y | A010 | BJ | | 115-199 |
| 5707 | 24 | | GK | | 3-0 | 27-32-21 | D01872 | | 1 | | GD01703 | DC.. | 2 | | 001-099 |
| 5707 | 24 | | GK | | 4-0 | 27-32-21 | D01872 | | 1 | | GD01705 | DC.. | 2 | | 115-199 |
| 5710 | 20 | | GK | | 7-0 | 27-62-11 | D00630 | | 8 | | D41032J | 51 | | | 001-099 |
| 5710 | 20 | | GK | | 5-0 | 27-62-11 | D00630 | | 8 | | D41030J | 13 | | | 115-199 |
| 5711 | 20 | | GK | | 10-0 | 27-62-11 | D00630 | | 7 | | TB0173Y | A019 | BJ | | ALL |
| 5712 | 22 | | GK | | 7-0 | 30-21-11 | D01508 | | A1 | | D41858J | 26 | | | ALL |
| 5713 | 22 | | GK | | 5-0 | 30-21-11 | D01508 | | A3 | | TB0179A | A016 | 2 | | 001-099 |
| 5713 | 22 | | GK | | 4-0 | 30-21-11 | D01508 | | A3 | | TB0179A | A016 | 2 | | 115-199 |
| 5714 | 22 | | GK | | 8-0 | 30-11-11 | D40570J | | 43 | | D00618 | A3 | | | 001-099 |
| 5714 | 22 | | GK | | 9-0 | 30-11-11 | D40570J | | 43 | | D00618 | A3 | | | 115-199 |
| 5715 | 22 | | GK | | 9-0 | 30-11-11 | D00618 | | A1 | | TB0178X | B030 | BJ | | 115-199 |
| 5716 | 22 | | GK | | 8-0 | 30-11-11 | D00618 | | A2 | | TB0178Y | A004 | BJ | | 001-099 |
| 5716 | 22 | | GK | | 9-0 | 30-11-11 | D00618 | | A2 | | TB0178Y | A004 | BJ | | 115-199 |
| 5717 | 24 | | GK | | 7-0 | 30-31-12 | TB0179A | A010 | 2 | | D41032J | 35 | | | 001-099 |
| 5717 | 24 | | GK | | 9-0 | 30-31-12 | TB0179C | A010 | 2 | | D41032J | 35 | | | 115-199 |
| 5718 | 22 | | GK | | 7-0 | 30-21-11 | D41858J | | 2 | | TB0179Y | A006 | BJ | | 001-099 |
| 5718 | 22 | | GK | | 6-0 | 30-21-11 | D41858J | | 2 | | TB0179Y | A011 | BJ | | 115-199 |
| 5719 | 22 | | GK | | 7-0 | 30-21-11 | D41994J | | 14 | | TB0179Y | A006 | BJ | | 001-099 |
| 5719 | 22 | | GK | | 6-0 | 30-21-11 | D41994J | | 14 | | TB0179Y | A011 | BJ | | 115-199 |
| 5720 | 22 | | GK | | 14-0 | 30-21-11 | D01508 | | A2 | | D06324 | 7 | | | 001-099 |
| 5720 | 22 | | GK | | 11-0 | 30-21-11 | D01508 | | A2 | | D06324 | 7 | | | 115-199 |
| 5721 | 22 | | GK | | 7-0 | 30-21-11 | D01508 | | X1 | * | D40738J | 14 | | | 001-099 |
| 5721 | 22 | | GK | | 8-0 | 30-21-11 | D01508 | | X1 | * | D40738J | 14 | | | 115-199 |
| 5722 | 22 | | GK | | 7-0 | 30-21-11 | D41994J | | 5 | | D01508 | X2 | | | 001-099 |
| 5722 | 22 | | GK | | 6-0 | 30-21-11 | D01508 | | X2 | | D41994J | 5 | | | 115-199 |
| 5723 | 24 | | GK | | 7-0 | 30-31-12 | TB0179A | C002 | 2 | | D41032J | 29 | | | 001-099 |
| 5723 | 24 | | GK | | 6-0 | 30-31-12 | TB0171C | C016 | 2 | | D41032J | 29 | | | 115-199 |
| 5725 | 22 | | GK | | 3-0 | 30-21-11 | D01510 | | X2 | | GD01704 | DC.. | 2 | | 001-099 |
| 5725 | 22 | | GK | | 2-0 | 30-21-11 | D01510 | | X2 | | GD01704 | DC.. | 2 | | 115-199 |
| 5726 | 22 | | GK | | 8-0 | 30-21-11 | D01510 | | X1 | | TB0178Y | C010 | BJ | | 001-099 |
| 5726 | 22 | | GK | | 9-0 | 30-21-11 | D01510 | | X1 | | TB0178Y | A027 | BJ | | 115-199 |
| 5729 | 24 | | GK | | 7-0 | 30-31-11 | D04090 | | B2 | | D41030J | 19 | | | 001-099 |
| 5729 | 24 | | GK | | 6-0 | 30-31-11 | D04090 | | B2 | | D41030J | 19 | | | 115-199 |
| 5730 | 24 | | GK | | 7-0 | 30-31-11 | D04090 | | A2 | | D41030J | 20 | | | 001-099 |
| 5730 | 24 | | GK | | 6-0 | 30-31-11 | D04090 | | A2 | | D41030J | 20 | | | 115-199 |
| 5731 | 24 | | GK | | 7-0 | 30-31-11 | D04090 | | B1 | | D41854J | 11 | | | 001-099 |
| 5731 | 24 | | GK | | 5-0 | 30-31-11 | D04090 | | B1 | | D41854J | 11 | | | 115-199 |
| 5732 | 24 | | GK | | 7-0 | 30-31-11 | D04090 | | A1 | | D41854J | 15 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 41

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5732 | 24 | | GK | | 5-0 | 30-31-11 | D04090 | | A1 | | D41854J | | 15 | | 115-199 |
| 5733 | 24 | | GK | | 5-0 | 30-31-12 | D40912J | | 5 | | D42176J | | 28 | | 001-099 |
| 5733 | 24 | | GK | | 5-0 | 30-31-12 | D40912J | | 5 | | D40862J | | 1 | | 115-199 |
| 5734 | 24 | | GK | | 5-0 | 30-31-12 | D40912J | | 11 | | D42176J | | 30 | | 001-099 |
| 5734 | 24 | | GK | | 5-0 | 30-31-12 | D40912J | | 11 | | D40864J | | 1 | | 115-199 |
| 5735 | 24 | | GK | | 7-0 | 30-31-12 | D02086 | | C1 | | D42176J | | 29 | | 001-099 |
| 5735 | 20 | | GK | | 7-0 | 30-31-12 | D02086 | | C1 | | D40862J | | 2 | | 115-199 |
| 5736 | 24 | | GK | | 7-0 | 30-31-12 | D40738J | | 6 | | TB0172Y | C001 | BJ | | 001-099 |
| 5736 | 24 | | GK | | 7-0 | 30-31-12 | D40738J | | 12 | | TB0172Y | C016 | BJ | | 115-199 |
| 5737 | 24 | | GK | | 2-0 | 30-31-12 | D02086 | | X1 | | TB0172Y | C001 | BJ | | 001-099 |
| 5737 | 24 | | GK | | 2-0 | 30-31-12 | D02086 | | X1 | | TB0172Y | C016 | BJ | | 115-199 |
| 5738 | 24 | | GK | | 2-0 | 30-31-12 | D02090 | | X1 | | TB0172Y | C001 | BJ | | 001-099 |
| 5738 | 24 | | GK | | 4-0 | 30-31-12 | D02090 | | X1 | | TB0172Y | C016 | BJ | | 115-199 |
| 5739 | 24 | | GK | | 8-0 | 30-31-12 | D02086 | | D2 | | D40594J | | 11 | | ALL |
| 5740 | 24 | | GK | | 8-0 | 30-31-12 | D40594J | | 12 | | D02090 | | D2 | | ALL |
| 5741 | 24 | | GK | | 9-0 | 30-31-12 | D02086 | | B1 | | TB0178X | A030 | BJ | | 115-199 |
| 5742 | 24 | | GK | | 2-0 | 30-31-12 | D02086 | | X2 | | GD01709 | DC.. | 2 | | ALL |
| 5743 | 24 | | GK | | 6-0 | 30-31-12 | D02086 | | D3 | | D41032J | | 15 | | ALL |
| 5744 | 24 | | GK | | 2-0 | 30-31-12 | D02086 | | B2 | | GD01709 | DC.. | 2 | | ALL |
| 5745 | 24 | | GK | | 2-0 | 30-31-12 | D02086 | | C3 | | GD01709 | DC.. | 2 | | ALL |
| 5746 | 24 | | GK | | 6-0 | 30-31-12 | D02086 | | A3 | | D41616J | | 29 | | 001-099 |
| 5746 | 24 | | GK | | 7-0 | 30-31-12 | D02086 | | A3 | | D41616J | | 29 | | 115-199 |
| 5747 | 24 | | GK | | 7-0 | 30-31-12 | D10750 | | C2 | | D41616J | | 4 | | 001-099 |
| 5747 | 24 | | GK | | 6-0 | 30-31-12 | D10750 | | C2 | | D41616J | | 4 | | 115-199 |
| 5748 | 24 | | GK | | 10-0 | 30-31-12 | D02090 | | B1 | | D10750 | | B2 | | 001-099 |
| 5748 | 24 | | GK | | 10-0 | 30-31-12 | D02090 | | B1 | | TB0177X | D003 | BJ | | 115-199 |
| 5749 | 24 | | GK | | 10-0 | 30-31-12 | D10750 | | B2 | | TB0177X | D003 | BJ | | 115-199 |
| 5750 | 24 | | GK | | 4-0 | 30-31-12 | D10750 | | B1 | | TB0179A | C010 | 2 | | 001-099 |
| 5750 | 24 | | GK | | 4-0 | 30-31-12 | D10750 | | B1 | | TB0179C | C010 | 2 | | 115-199 |
| 5751 | 24 | | GK | | 3-0 | 30-31-12 | D10750 | | A1 | | TB0179A | A002 | 2 | | 001-099 |
| 5751 | 24 | | GK | | 4-0 | 30-31-12 | D10750 | | A1 | | TB0171C | A016 | 2 | | 115-199 |
| 5752 | 24 | | GK | | 7-0 | 30-31-12 | D03212 | | C2 | * | D41032J | | 32 | | 001-099 |
| 5752 | 24 | | GK | | 9-0 | 30-31-12 | D03212 | | C2 | | TB0178Y | A009 | BJ | | 115-199 |
| 5753 | 24 | | GK | | 3-0 | 30-31-12 | D03212 | | C1 | | GD01703 | AC.. | 2 | | 001-099 |
| 5753 | 24 | | GK | | 4-0 | 30-31-12 | D03212 | | C1 | | GD01704 | AC.. | 2 | | 115-199 |
| 5755 | 24 | | GK | | 7-0 | 30-31-12 | D10750 | | C3 | | D41032J | | 13 | | 001-099 |
| 5755 | 24 | | GK | | 6-0 | 30-31-12 | D10750 | | C3 | | D41032J | | 13 | | 115-199 |
| 5756 | 24 | | GK | | 7-0 | 30-31-12 | D10750 | | D3 | | D41032J | | 14 | | 001-099 |
| 5756 | 24 | | GK | | 6-0 | 30-31-12 | D10750 | | D3 | | D41032J | | 14 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 42

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5757 | 24 | | GK | | 7-0 | 30-31-12 | | D10750 | | D2 | | D41616J | | 1 | | 001-099 |
| 5757 | 24 | | GK | | 6-0 | 30-31-12 | | D10750 | | D2 | | D41616J | | 1 | | 115-199 |
| 5759 | 24 | | GK | | 6-0 | 30-31-12 | | D02090 | | A3 | | D41616J | | 28 | | 001-099 |
| 5759 | 24 | | GK | | 7-0 | 30-31-12 | | D02090 | | A3 | | D41616J | | 28 | | 115-199 |
| 5760 | 24 | | GK | | 7-0 | 30-31-12 | | D02090 | | C1 | | D42176J | | 31 | | 001-099 |
| 5760 | 24 | | GK | | 6-0 | 30-31-12 | | D02090 | | C1 | | D40864J | | 2 | | 115-199 |
| 5761 | 24 | | GK | | 6-0 | 30-31-12 | | D02090 | | D3 | | D41032J | | 16 | | ALL |
| 5762 | 24 | | GK | | 3-0 | 30-31-12 | | D10750 | | B3 | | GD01704 | AC.. | 2 | | 001-099 |
| 5762 | 24 | | GK | | 4-0 | 30-31-12 | | D10750 | | B3 | | GD01704 | AC.. | 2 | | 115-199 |
| 5763 | 24 | | GK | | 2-0 | 30-31-12 | | D02090 | | X2 | | GD01709 | DC.. | 2 | | ALL |
| 5764 | 24 | | GK | | 2-0 | 30-31-12 | | D02090 | | C3 | | GD01709 | DC.. | 2 | | ALL |
| 5765 | 24 | | GK | | 2-0 | 30-31-12 | | D02090 | | B2 | | GD01709 | DC.. | 2 | | ALL |
| 5766 | 24 | | GK | | 3-0 | 30-31-12 | | D10750 | | A3 | | GD01704 | AC.. | 2 | | 001-099 |
| 5766 | 24 | | GK | | 4-0 | 30-31-12 | | D10750 | | A3 | | GD01704 | AC.. | 2 | | 115-199 |
| 5767 | 24 | | GK | | 3-0 | 30-33-11 | | D02776 | | A3 | | D03212 | | B1 | * | 001-099 |
| 5767 | 24 | | GK | | 9-0 | 30-33-11 | | D02776 | | A3 | | TB0178Y | C010 | BJ | | 115-199 |
| 5768 | 24 | | GK | | 7-0 | 30-33-11 | | D02776 | | X1 | | D40718J | | 18 | | 001-099 |
| 5768 | 24 | | GK | | 8-0 | 30-33-11 | | D02776 | | X1 | | D40718J | | 18 | | 115-199 |
| 5769 | 24 | | GK | | 4-0 | 30-33-11 | | D02776 | | A2 | | D03212 | | B3 | | ALL |
| 5770 | 20 | | GK | | 9-0 | 30-33-11 | | D41909J | | 31 | | TB0171Y | A002 | BJ | | 115-199 |
| 5771 | 24 | | GK | | 3-0 | 30-33-11 | | D02776 | | C3 | | GD01706 | DC.. | 2 | | 001-099 |
| 5771 | 24 | | GK | | 4-0 | 30-33-11 | | D02776 | | C3 | | GD01706 | DC.. | 2 | | 115-199 |
| 5773 | 24 | | GK | | 3-0 | 30-33-11 | | D02776 | | X2 | | GD01706 | DC.. | 2 | | 001-099 |
| 5773 | 24 | | GK | | 4-0 | 30-33-11 | | D02776 | | X2 | | GD01706 | DC.. | 2 | | 115-199 |
| 5774 | 20 | | GK | | 3-0 | 30-33-11 | | D02776 | | B1 | | GD01706 | AC.. | 2 | | 001-099 |
| 5774 | 20 | | GK | | 4-0 | 30-33-11 | | D02776 | | B1 | | GD01706 | DC.. | 2 | | 115-199 |
| 5775 | 20 | | GK | | 3-0 | 30-33-11 | | D02776 | | C1 | | D03212 | | D2 | * | 001-099 |
| 5775 | 20 | | GK | | 4-0 | 30-33-11 | | D02776 | | C1 | | TB0171Y | A001 | BJ | | 115-199 |
| 5776 | 20 | | GK | | 2-0 | 30-33-11 | | D00616 | | B2 | | D03212 | | D2 | * | 001-099 |
| 5776 | 20 | | GK | | 4-0 | 30-33-11 | | D00616 | | B2 | | TB0171Y | A001 | BJ | | 115-199 |
| 5777 | 20 | | GK | | 4-0 | 30-33-11 | | D03212 | | D2 | | TB0171Y | A001 | BJ | | 115-199 |
| 5778 | 20 | | GK | | 2-0 | 30-33-11 | | D00616 | | B3 | | D03212 | | D1 | * | 001-099 |
| 5778 | 20 | | GK | | 4-0 | 30-33-11 | | D00616 | | B3 | | TB0171Y | A002 | BJ | | 115-199 |
| 5779 | 20 | | GK | | 9-0 | 30-33-11 | | D03212 | | D1 | * | D41909J | | 31 | | 001-099 |
| 5779 | 20 | | GK | | 4-0 | 30-33-11 | | D03212 | | D1 | | TB0171Y | A002 | BJ | | 115-199 |
| 5787 | 20 | | GK | | 9-0 | 30-71-11 | | D00620 | | C1 | | TB0177X | A004 | BJ | | 001-099 |
| 5787 | 20 | | GK | | 8-0 | 30-71-11 | | D00620 | | C1 | | TB0178G | | 13 | 2 | 115-199 |
| 5788 | 24 | | GK | | 7-0 | 21-51-11 | | D00630 | | 2 | | D41854J | | 6 | | 001-099 |
| 5788 | 24 | | GK | | 6-0 | 21-51-11 | | D00630 | | 2 | | D40064J | | 58 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 43

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5835 | 22 | | GK | | 5-0 | 32-09-12 | | D41616J | | 14 | | TB0171Y | A004 | BJ | | 115-199 |
| 5836 | 22 | | GK | | 3-0 | 32-09-12 | | D00616 | | X2 | * | D00618 | X2 | | * | 001-002 |
| 5836 | 22 | | GK | | 5-0 | 32-09-12 | | D00616 | | X2 | * | D00618 | X2 | | * | 003-099 |
| 5836 | 22 | | GK | | 4-0 | 32-09-12 | | D00616 | | X2 | * | TB0171Y | A004 | BJ | | 115-199 |
| 5837 | 22 | | GK | | 3-0 | 32-09-12 | | D00616 | | X1 | * | D00618 | X1 | | * | 001-002 |
| 5837 | 22 | | GK | | 5-0 | 32-09-12 | | D00616 | | X1 | * | D00618 | X1 | | * | 003-099 |
| 5837 | 22 | | GK | | 4-0 | 32-09-12 | | D00616 | | X1 | | D00634 | X1 | | * | 115-199 |
| 5838 | 22 | | GK | | 3-0 | 32-09-12 | | D00630 | | 6 | | TB0170Z | 2 | BJ | | 001-099 |
| 5838 | 22 | | GK | | 3-0 | 32-09-12 | | D00630 | | 6 | | TB0171Z | 6 | BJ | | 115-199 |
| 5839 | 22 | | GK | | 3-0 | 32-09-12 | | D00630 | | 12 | | TB0171Z | 6 | BJ | | 001-099 |
| 5839 | 22 | | GK | | 3-0 | 32-09-12 | | D00630 | | 12 | | TB0171Z | 7 | BJ | | 115-199 |
| 5840 | 22 | | GK | | 3-0 | 32-09-12 | | D00624 | | 6 | | TB0170Z | 2 | BJ | | 001-099 |
| 5840 | 22 | | GK | | 4-0 | 32-09-12 | | D00624 | | 6 | | TB0171Z | 6 | BJ | | 115-199 |
| 5841 | 22 | | GK | | 3-0 | 32-09-12 | | D00624 | | 12 | | TB0171Z | 6 | BJ | | 001-099 |
| 5841 | 22 | | GK | | 4-0 | 32-09-12 | | D00624 | | 12 | | TB0171Z | 7 | BJ | | 115-199 |
| 5842 | 22 | | GK | | 3-0 | 32-09-12 | | D00628 | | 6 | | TB0171Z | 4 | BJ | | 001-099 |
| 5842 | 22 | | GK | | 3-0 | 32-09-12 | | D00628 | | 6 | | TB0171Z | 6 | BJ | | 115-199 |
| 5843 | 22 | | GK | | 3-0 | 32-09-12 | | D00628 | | 12 | | TB0171Z | 6 | BJ | | 001-099 |
| 5843 | 22 | | GK | | 3-0 | 32-09-12 | | D00628 | | 12 | | TB0171Z | 7 | BJ | | 115-199 |
| 5844 | 22 | | GK | | 3-0 | 32-09-12 | | D00610 | | 12 | | TB0170Z | 10 | BJ | | 001-099 |
| 5844 | 22 | | GK | | 3-0 | 32-09-12 | | D00610 | | 12 | | TB0171Z | 11 | BJ | | 115-199 |
| 5845 | 22 | | GK | | 3-0 | 32-09-12 | | D00610 | | 6 | | TB0170Z | 2 | BJ | | 001-099 |
| 5845 | 22 | | GK | | 3-0 | 32-09-12 | | D00610 | | 6 | | TB0171Z | 12 | BJ | | 115-199 |
| 5846 | 22 | | GK | | 2-0 | 32-09-12 | | D00616 | | X1 | * | D00634 | X1 | | | 001-002 |
| 5846 | 22 | | GK | | 5-0 | 32-09-12 | | D00616 | | X1 | * | D00634 | X1 | | | 003-099 |
| 5846 | 22 | | GK | | 4-0 | 32-09-12 | | D00626 | | X1 | | TB0171Z | 10 | BJ | | 115-199 |
| 5847 | 22 | | GK | | 3-0 | 32-09-12 | | D00626 | | X2 | | TB0171Z | 5 | BJ | | 001-099 |
| 5847 | 22 | | GK | | 4-0 | 32-09-12 | | D00626 | | X2 | | TB0180Z | 4 | BJ | | 115-199 |
| 5848 | 22 | | GK | | 3-0 | 32-09-12 | | D01872 | | 6 | | TB0170Z | 1 | BJ | | 001-099 |
| 5848 | 22 | | GK | | 4-0 | 32-09-12 | | D01872 | | 6 | | TB0171Z | 6 | BJ | | 115-199 |
| 5849 | 22 | | GK | | 7-0 | 32-09-12 | | D01872 | | 12 | | D41616J | 15 | | | 001-099 |
| 5849 | 22 | | GK | | 5-0 | 32-09-12 | | D01872 | | 12 | | D41616J | 15 | | | 115-199 |
| 5850 | 22 | | GK | | 3-0 | 32-09-12 | | D01866 | | 12 | | TB0171Z | 3 | BJ | | 001-099 |
| 5850 | 22 | | GK | | 3-0 | 32-09-12 | | D01866 | | 12 | | TB0171Z | 8 | BJ | | 115-199 |
| 5851 | 22 | | GK | | 3-0 | 32-09-12 | | D01866 | | 6 | | TB0170Z | 1 | BJ | | 001-099 |
| 5851 | 22 | | GK | | 3-0 | 32-09-12 | | D01866 | | 6 | | TB0171Z | 10 | BJ | | 115-199 |
| 5852 | 22 | | GK | | 3-0 | 32-09-12 | | D04090 | | X1 | * | TB0171Y | A002 | BJ | | 001-099 |
| 5852 | 22 | | GK | | 4-0 | 32-09-12 | | D04090 | | X1 | | TB0171Z | 9 | BJ | | 115-199 |
| 5853 | 22 | | GK | | 2-0 | 32-09-12 | | D04090 | | X2 | | TB0171Z | 3 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 45

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | |
| 5853 | 22 | GK | | | 4-0 | 32-09-12 | D04090 | | X2 | | TB0171Z | 8 | BJ | | 115-199 |
| 5854 | 22 | GK | | | 3-0 | 32-09-12 | D01864 | | 12 | | D00616 | X2 | | * | 001-002 |
| 5854 | 22 | GK | | | 5-0 | 32-09-12 | D01864 | | 12 | | D00616 | X2 | | * | 003-099 |
| 5854 | 22 | GK | | | 4-0 | 32-09-12 | D01864 | | 12 | | D00616 | X2 | | * | 115-199 |
| 5855 | 22 | GK | | | 3-0 | 32-09-12 | D01864 | | 6 | | SM00062 | | W | | 001-002 |
| 5855 | 22 | GK | | | 5-0 | 32-09-12 | D01864 | | 6 | | TB0171Z | 14 | BJ | | 003-099 |
| 5855 | 22 | GK | | | 4-0 | 32-09-12 | D01864 | | 6 | | SM00062 | | W | | 115-199 |
| 5856 | 22 | GK | | | 3-0 | 32-09-12 | D00636 | | 12 | | TB0171Z | 6 | BJ | | 001-099 |
| 5856 | 22 | GK | | | 4-0 | 32-09-12 | D00636 | | 12 | | TB0171Z | 7 | BJ | | 115-199 |
| 5857 | 22 | GK | | | 3-0 | 32-09-12 | D00636 | | 6 | | TB0170Z | 1 | BJ | | 001-099 |
| 5857 | 22 | GK | | | 4-0 | 32-09-12 | D00636 | | 6 | | TB0171Z | 12 | BJ | | 115-199 |
| 5858 | 22 | GK | | | 3-0 | 32-09-12 | D10750 | | X1 | | D04090 | X1 | | * | 001-002 |
| 5858 | 22 | GK | | | 3-0 | 32-09-12 | D10750 | | X1 | * | D04090 | X1 | | * | 003-099 |
| 5858 | 22 | GK | | | 4-0 | 32-09-12 | D10750 | | X1 | | TB0180Z | 3 | BJ | | 115-199 |
| 5860 | 22 | GK | | | 3-0 | 32-09-12 | D00612 | | 12 | | TB0170Z | 10 | BJ | | 001-099 |
| 5860 | 22 | GK | | | 4-0 | 32-09-12 | D00612 | | 12 | | TB0171Z | 11 | BJ | | 115-199 |
| 5861 | 22 | GK | | | 3-0 | 32-09-12 | D00612 | | 6 | | TB0170Z | 2 | BJ | | 001-099 |
| 5861 | 22 | GK | | | 4-0 | 32-09-12 | D00612 | | 6 | | TB0171Z | 12 | BJ | | 115-199 |
| 5862 | 22 | GK | | | 2-0 | 32-09-12 | D00620 | | X1 | | D00626 | X1 | | * | 001-002 |
| 5862 | 22 | GK | | | 5-0 | 32-09-12 | D00620 | | X1 | | D00626 | X1 | | * | 003-099 |
| 5862 | 22 | GK | | | 4-0 | 32-09-12 | D00620 | | X1 | | TB0171Z | 9 | BJ | | 115-199 |
| 5863 | 22 | GK | | | 3-0 | 32-09-12 | D00620 | | X2 | | TB0171Z | 5 | BJ | | 001-099 |
| 5863 | 22 | GK | | | 4-0 | 32-09-12 | D00620 | | X2 | | TB0180Z | 4 | BJ | | 115-199 |
| 5864 | 22 | GK | | | 3-0 | 32-09-12 | D00632 | | 6 | | TB0171Z | 4 | BJ | | 001-099 |
| 5864 | 22 | GK | | | 4-0 | 32-09-12 | D00632 | | 6 | | TB0171Z | 9 | BJ | | 115-199 |
| 5865 | 22 | GK | | | 3-0 | 32-09-12 | D00632 | | 12 | | TB0171Z | 5 | BJ | | 001-099 |
| 5865 | 22 | GK | | | 4-0 | 32-09-12 | D00632 | | 12 | | TB0180Z | 4 | BJ | | 115-199 |
| 5866 | 22 | GK | | | 3-0 | 32-09-12 | D01868 | | 6 | | TB0170Z | 2 | BJ | | 001-099 |
| 5866 | 22 | GK | | | 3-0 | 32-09-12 | D01868 | | 6 | | TB0171Z | 10 | BJ | | 115-199 |
| 5867 | 22 | GK | | | 3-0 | 32-09-12 | D01868 | | 12 | | TB0171Z | 3 | BJ | | 001-099 |
| 5867 | 22 | GK | | | 3-0 | 32-09-12 | D01868 | | 12 | | TB0171Z | 8 | BJ | | 115-199 |
| 5868 | 22 | GK | | | 3-0 | 32-09-12 | D01870 | | 6 | | TB0170Z | 1 | BJ | | 001-099 |
| 5868 | 22 | GK | | | 3-0 | 32-09-12 | D01870 | | 6 | | TB0171Z | 10 | BJ | | 115-199 |
| 5869 | 22 | GK | | | 7-0 | 32-09-12 | D01870 | | 12 | | D41616J | 18 | | | 001-099 |
| 5869 | 22 | GK | | | 5-0 | 32-09-12 | D01870 | | 12 | | D41616J | 18 | | | 115-199 |
| 5870 | 22 | GK | | | 3-0 | 32-09-12 | D00622 | | 12 | | TB0170Z | 10 | BJ | | 001-099 |
| 5870 | 22 | GK | | | 4-0 | 32-09-12 | D00622 | | 12 | | TB0171Z | 11 | BJ | | 115-199 |
| 5871 | 22 | GK | | | 3-0 | 32-09-12 | D00622 | | 6 | | TB0170Z | 2 | BJ | | 001-099 |
| 5871 | 22 | GK | | | 4-0 | 32-09-12 | D00622 | | 6 | | TB0171Z | 12 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 46

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 5872 | 22 | | GK | | 3-0 | 32-09-12 | D00614 | | 12 | | TB0170Z | 10 | BJ | | 001-099 |
| 5872 | 22 | | GK | | 4-0 | 32-09-12 | D00614 | | 12 | | TB0171Z | 11 | BJ | | 115-199 |
| 5873 | 22 | | GK | | 3-0 | 32-09-12 | D00614 | | 6 | | TB0170Z | 2 | BJ | | 001-099 |
| 5873 | 22 | | GK | | 4-0 | 32-09-12 | D00614 | | 6 | | TB0171Z | 12 | BJ | | 115-199 |
| 5874 | 22 | | GK | | 3-0 | 32-09-12 | D02676 | | 6 | | TB0171Z | 4 | BJ | | 001-099 |
| 5874 | 22 | | GK | | 3-0 | 32-09-12 | D02676 | | 6 | | TB0171Z | 12 | BJ | | 115-199 |
| 5875 | 22 | | GK | | 3-0 | 32-09-12 | D02676 | | 12 | | TB0170Z | 10 | BJ | | 001-099 |
| 5875 | 22 | | GK | | 3-0 | 32-09-12 | D02676 | | 12 | | TB0171Z | 11 | BJ | | 115-199 |
| 5876 | 22 | | GK | | 7-0 | 32-09-12 | D41616J | | 12 | | TB0171Z | 6 | BJ | | 001-099 |
| 5876 | 22 | | GK | | 5-0 | 32-09-12 | D41616J | | 12 | | TB0171Z | 7 | BJ | | 115-199 |
| 5877 | 22 | | GK | | 1-0 | 32-09-12 | TB0171Y | A002 | BJ | | TB0171Z | 4 | BJ | | 001-099 |
| 5877 | 22 | | GK | | 2-0 | 32-09-12 | TB0171Z | 6 | BJ | | TB0171Z | 10 | BJ | | 115-199 |
| 5878 | 22 | | GK | | 7-0 | 32-09-12 | D41616J | | 16 | | TB0171Z | 5 | BJ | | 001-099 |
| 5878 | 22 | | GK | | 5-0 | 32-09-12 | D41616J | | 16 | | TB0180Z | 4 | BJ | | 115-199 |
| 5880 | 22 | | GK | | 7-0 | 32-09-12 | D41616J | | 13 | | TB0171Z | 3 | BJ | | 001-099 |
| 5880 | 22 | | GK | | 5-0 | 32-09-12 | D41616J | | 13 | | TB0171Z | 8 | BJ | | 115-199 |
| 5881 | 22 | | GK | | 7-0 | 32-09-12 | D41616J | | 11 | | TB0170Z | 10 | BJ | | 001-099 |
| 5881 | 22 | | GK | | 5-0 | 32-09-12 | D41616J | | 11 | | TB0171Z | 11 | BJ | | 115-199 |
| 5882 | 22 | | GK | | 2-0 | 32-09-12 | TB0171Z | 9 | BJ | | TB0171Z | 12 | BJ | | 115-199 |
| 5883 | 22 | | GK | | 7-0 | 32-09-12 | D40718J | | 11 | | TB0170Z | 1 | BJ | | 001-099 |
| 5883 | 22 | | GK | | 8-0 | 32-09-12 | D40718J | | 11 | | TB0171Z | 12 | BJ | | 115-199 |
| 5884 | 22 | | GK | | 1-0 | 32-09-12 | TB0170Z | 2 | BJ | | TB0170Z | 1 | BJ | | 001-099 |
| 5884 | 22 | | GK | | 2-0 | 32-09-12 | TB0171Z | 9 | BJ | | TB0171Z | 10 | BJ | | 115-199 |
| 5888 | 22 | | GK | | 7-0 | 32-31-11 | D00626 | A1 | | | D41487J | 35 | | | ALL |
| 5889 | 22 | | GK | | 3-0 | 32-31-11 | D00626 | A2 | | | GD01704 | DC.. | 2 | | 001-099 |
| 5889 | 22 | | GK | | 4-0 | 32-31-11 | D00626 | A2 | | | GD01705 | DC.. | 2 | | 115-199 |
| 5892 | 22 | | GK | | 3-0 | 32-61-12 | D03220 | | 7 | | TB0170Y | A003 | BJ | | 001-099 |
| 5892 | 22 | | GK | | 4-0 | 32-61-12 | D03220 | | 7 | | TB0170Y | A016 | BJ | | 115-199 |
| 5893 | 22 | | GK | | 7-0 | 32-61-12 | D03220 | | 2 | | D41616J | 19 | | | ALL |
| 5894 | 22 | | GK | | 7-0 | 32-61-12 | D03220 | | 3 | | D41616J | 20 | | | ALL |
| 5895 | 22 | | GK | | 7-0 | 32-61-12 | D03220 | | 5 | | D41487J | 54 | | | ALL |
| 5900 | 22 | | GK | | 7-0 | 32-61-12 | D03222 | | 5 | | D41487J | 53 | | | 001-099 |
| 5900 | 22 | | GK | | 6-0 | 32-61-12 | D03222 | | 5 | | D41487J | 53 | | | 115-199 |
| 5901 | 22 | | GK | | 7-0 | 32-61-12 | D03222 | | 3 | | D41616J | 21 | | | 001-099 |
| 5901 | 22 | | GK | | 6-0 | 32-61-12 | D03222 | | 3 | | D41616J | 21 | | | 115-199 |
| 5904 | 22 | | GK | | 3-0 | 32-61-12 | D03222 | | 7 | | TB0170Y | A003 | BJ | | 001-099 |
| 5904 | 22 | | GK | | 4-0 | 32-61-12 | D03222 | | 7 | | TB0170Y | A016 | BJ | | 115-199 |
| 5905 | 22 | | GK | | 6-0 | 32-61-12 | D03222 | | 2 | | D41616J | 23 | | | ALL |
| 5914 | 24 | | GK | | 8-0 | 34-12-22 | D00624 | | 1 | | D42176J | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 47

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 5914 | 24 | | GK | | 9-0 | 34-12-22 | D00624 | | | 1 | | D42176J | 18 | | | 115-199 |
| 5915 | 24 | | GK | | 6-0 | 34-12-22 | D00624 | | | 2 | | D41487J | 22 | | | 001-099 |
| 5915 | 24 | | GK | | 5-0 | 34-12-22 | D00624 | | | 2 | | D41487J | 22 | | | 115-199 |
| 5917 | 24 | | GK | | 6-0 | 34-12-22 | D41487J | | | 23 | | D02086 | A2 | | | 001-099 |
| 5917 | 24 | | GK | | 7-0 | 34-12-22 | D41487J | | | 23 | | D02086 | A2 | | | 115-199 |
| 5920 | 24 | | GK | | 6-0 | 34-12-22 | D41487J | | | 24 | | D02776 | D3 | | | ALL |
| 5921 | 24 | | GK | | 2-0 | 34-12-22 | D02776 | | | B2 | | GD01706 | DC.. | 2 | | 001-099 |
| 5921 | 24 | | GK | | 4-0 | 34-12-22 | D02776 | | | B2 | | GD01706 | DC.. | 2 | | 115-199 |
| 5922 | 24 | | GK | | 6-0 | 34-12-22 | D02094 | | | D3 | | D41487J | 25 | | | ALL |
| 5923 | 24 | | GK | | 3-0 | 34-46-12 | D01868 | | | 3 | | GD01701 | DC.. | 2 | | 001-099 |
| 5923 | 24 | | GK | | 4-0 | 34-46-12 | D01868 | | | 3 | | GD01702 | DC.. | 2 | | 115-199 |
| 5924 | 24 | | GK | | 7-0 | 34-46-12 | D01868 | | | 5 | | D41739J | 35 | | | 001-099 |
| 5924 | 24 | | GK | | 6-0 | 34-46-12 | D01868 | | | 5 | | D41739J | 35 | | | 115-199 |
| 5925 | 24 | | GK | | 6-0 | 34-53-21 | D00612 | | | 7 | | D41487J | 39 | | | ALL |
| 5926 | 24 | | GK | | 3-0 | 34-53-21 | D00612 | | | 8 | | GD01702 | DC.. | 2 | | 001-099 |
| 5926 | 24 | | GK | | 4-0 | 34-53-21 | D00612 | | | 8 | | GD01702 | DC.. | 2 | | 115-199 |
| 5927 | 24 | | GK | | 6-0 | 34-55-21 | D00636 | | | 5 | | D41487J | 21 | | | 001-099 |
| 5927 | 24 | | GK | | 5-0 | 34-55-21 | D00636 | | | 5 | | D41487J | 21 | | | 115-199 |
| 5928 | 24 | | GK | | 3-0 | 34-55-21 | D00636 | | | 3 | | GD01703 | DC.. | 2 | | 001-099 |
| 5928 | 24 | | GK | | 4-0 | 34-55-21 | D00636 | | | 3 | | GD01705 | DC.. | 2 | | 115-199 |
| 5929 | 24 | | GK | | 7-0 | 34-61-24 | D00610 | | | 7 | | D41487J | 2 | | | 001-099 |
| 5929 | 24 | | GK | | 6-0 | 34-61-24 | D00610 | | | 7 | | D41487J | 2 | | | 115-199 |
| 5930 | 24 | | GK | | 3-0 | 34-61-24 | D00610 | | | 8 | | GD01702 | DC.. | 2 | | 001-099 |
| 5930 | 24 | | GK | | 5-0 | 34-61-24 | D00610 | | | 8 | | GD01702 | DC.. | 2 | | 115-199 |
| 5931 | 22 | | GK | | 8-0 | 49-61-11 | D00636 | | | 1 | | D41684J | 7 | | | 001-099 |
| 5931 | 22 | | GK | | 9-0 | 49-61-11 | D00636 | | | 1 | | D41684J | 7 | | | 115-199 |
| 5932 | 22 | | GK | | 8-0 | 49-61-11 | D00636 | | | 13 | | D41684J | 8 | | | 001-099 |
| 5932 | 22 | | GK | | 9-0 | 49-61-11 | D00636 | | | 13 | | D41684J | 8 | | | 115-199 |
| 5933 | 22 | | GK | | 9-0 | 34-61-25 | D02526 | | | X1 | | D41909J | 42 | | | ALL |
| 5934 | 22 | | GK | | 8-0 | 76-11-21 | D00634 | | | B1 | | TB0178X | B022 | BJ | | 001-099 |
| 5934 | 22 | | GK | | 9-0 | 76-11-21 | D00634 | | | B1 | | TB0178X | D005 | BJ | | 115-199 |
| 5935 | 22 | | GK | | 8-0 | 76-11-21 | D00634 | | | B2 | | TB0178Z | 11 | BJ | | 001-099 |
| 5935 | 22 | | GK | | 9-0 | 76-11-21 | D00634 | | | B2 | | TB0178Z | 21 | BJ | | 115-199 |
| 5936 | 22 | | GK | | 9-0 | 78-34-21 | D00616 | | | A2 | | D02640 | A2 | | * | 001-002 |
| 5936 | 22 | | GK | | 14-0 | 78-34-21 | D00616 | | | A2 | | D02640 | A2 | | * | 003-099 |
| 5936 | 22 | | GK | | 11-0 | 78-34-21 | D00616 | | | A2 | | D02640 | A2 | | * | 115-199 |
| 5937 | 22 | | GK | | 5-0 | 78-34-21 | SM00029 | | | | WI | D41478J | 31 | | | 001-002 |
| 5937 | 22 | | GK | | 9-0 | 78-34-21 | D00616 | | | A1 | | D41478J | 31 | | | 003-099 |
| 5937 | 22 | | GK | | 4-0 | 78-34-21 | D41478J | | | 31 | | SM00029 | | WI | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 48

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 5938 | 22 | | GK | | 3-0 | 34-61-25 | D02526 | | X2 | | | GD01704 | DC.. | 2 | | 001-099 | |
| 5938 | 22 | | PA | | 9-0 | 34-61-25 | D41909J | | 27 | | | D02526 | X2 | | | 115-199 | |
| 5939 | 22 | | GK | | 3-0 | 31-31-61 | D01868 | | 14 | | | GD01701 | DC.. | 2 | | 001-099 | |
| 5939 | 22 | | GK | | 3-0 | 31-31-13 | D01868 | | 14 | | | GD01701 | DC.. | 2 | | 115-199 | |
| 5942 | 24 | | GK | | 2-0 | 30-32-11 | D02094 | | X2 | | | GD01706 | DC.. | 2 | | 001-099 | |
| 5942 | 24 | | GK | | 4-0 | 30-32-11 | D02094 | | X2 | | | GD01706 | DC.. | 2 | | 115-199 | |
| 5943 | 24 | | GK | | 2-0 | 30-32-11 | D02094 | | B2 | | | GD01706 | DC.. | 2 | | 001-099 | |
| 5943 | 24 | | GK | | 4-0 | 30-32-11 | D02094 | | B2 | | | GD01706 | DC.. | 2 | | 115-199 | |
| 5944 | 22 | | GK | | 2-0 | 30-32-11 | D02094 | | B1 | | | GD01706 | AC.. | 2 | | 001-099 | |
| 5944 | 22 | | GK | | 4-0 | 30-32-11 | D02094 | | B1 | | | GD01706 | AC.. | 2 | | 115-199 | |
| 5945 | 24 | | GK | | 9-0 | 30-32-11 | D02094 | | X1 | | | D40594J | 42 | | | ALL | |
| 5946 | 24 | | GK | | 6-0 | 30-32-11 | TB0178Y | C006 | BJ | | | D40594J | 26 | | | 001-099 | |
| 5946 | 24 | | GK | | 9-0 | 30-32-11 | TB0179Y | A014 | BJ | | | D40594J | 26 | | | 115-199 | |
| 5947 | 24 | | GK | | 8-0 | 30-32-11 | TB0178Y | C006 | BJ | | | D02094 | D2 | | | 001-099 | |
| 5947 | 24 | | GK | | 4-0 | 30-32-11 | TB0179Y | A014 | BJ | | | D02094 | D2 | | | 115-199 | |
| 5948 | 24 | | GK | | 6-0 | 30-32-11 | TB0178Y | C006 | BJ | | | D41616J | 32 | | | 001-099 | |
| 5948 | 24 | | GK | | 5-0 | 30-32-11 | TB0179Y | A014 | BJ | | | D41616J | 32 | | | 115-199 | |
| 5949 | 22 | | GK | | 9-0 | 30-32-11 | D02094 | | C1 | | | D41487J | 19 | | | 115-199 | |
| 5950 | 24 | | GK | | 8-0 | 30-32-11 | D03212 | | X1 | | | D41860J | 31 | | | 001-099 | |
| 5950 | 24 | | GK | | 9-0 | 30-32-11 | D03212 | | X1 | | | D41860J | 31 | | | 115-199 | |
| 5951 | 24 | | GK | | 1-0 | 30-32-11 | D03212 | | X2 | | | GD01703 | DC.. | 2 | | 001-099 | |
| 5951 | 24 | | GK | | 4-0 | 30-32-11 | D03212 | | X2 | | | GD01703 | DC.. | 2 | | 115-199 | |
| 5952 | 22 | | GK | | 7-0 | 30-32-11 | D41487J | | 19 | | | D02094 | C1 | | | 001-099 | |
| 5952 | 22 | | GK | | 9-0 | 30-32-11 | D03212 | | A1 | | | TB0178Z | 22 | BJ | | 115-199 | |
| 5953 | 22 | | GK | | 3-0 | 30-32-11 | D00634 | | C3 | * | | D03212 | A1 | | * | 001-099 | |
| 5953 | 22 | | GK | | 9-0 | 30-32-11 | D00634 | | C3 | | | TB0178Z | 22 | BJ | | 115-199 | |
| 5954 | 22 | | GK | | 7-0 | 30-32-11 | D03212 | | A2 | * | | D41487J | 20 | | | 001-099 | |
| 5954 | 22 | | GK | | 9-0 | 30-32-11 | D03212 | | A2 | | | TB0178Z | 25 | BJ | | 115-199 | |
| 5955 | 22 | | GK | | 3-0 | 30-32-11 | D00634 | | C2 | | | D03212 | A2 | | * | 001-099 | |
| 5955 | 22 | | GK | | 9-0 | 30-32-11 | D00634 | | C2 | | | TB0178Z | 25 | BJ | | 115-199 | |
| 5961 | 22 | | GK | | 3-0 | 49-61-11 | D00636 | | 7 | | | GD01703 | DC.. | 2 | | 001-099 | |
| 5961 | 22 | | GK | | 9-0 | 49-61-11 | D00636 | | 8 | | | D41684J | 15 | | | 115-199 | |
| 5962 | 22 | | GK | | 8-0 | 49-61-11 | D00636 | | 8 | | | D41684J | 15 | | | 001-099 | |
| 5962 | 22 | | GK | | 2-0 | 49-61-11 | D00636 | | 7 | | | GD01703 | DC.. | 2 | | 115-199 | |
| 5976 | 24 | | GK | | 7-0 | 21-61-31 | D41546J | | 24 | | | D02576 | B1 | | | 001-099 | |
| 5976 | 24 | | GK | | 6-0 | 21-61-31 | D41546J | | 24 | | | D02576 | B1 | | | 115-199 | |
| 5977 | 24 | | GK | | 3-0 | 21-61-31 | D04348 | | 6 | | | GD01701 | DC.. | 2 | | 001-099 | |
| 5977 | 24 | | GK | | 4-0 | 21-61-31 | D04348 | | 6 | | | GD01703 | DC.. | 2 | | 115-199 | |
| 5978 | 24 | | GK | | 3-0 | 21-51-23 | D01868 | | 2 | | | GD01701 | DC.. | 2 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 49

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | |
| 5978 | 24 | GK | | | 4-0 | 21-51-23 | D01868 | | 2 | | GD01702 | DC.. | 2 | | 115-199 |
| 5979 | 24 | GK | | | 7-0 | 21-51-23 | D01868 | | 1 | | D41546J | 47 | | | 001-099 |
| 5979 | 24 | GK | | | 5-0 | 21-51-23 | D01868 | | 1 | | D41546J | 47 | | | 115-199 |
| 5981 | 24 | GK | | | 1-0 | 21-61-11 | TB0179A | C007 | 2 | | TB0179A | C008 | 2 | | 001-099 |
| 5981 | 24 | GK | | | 1-0 | 21-61-11 | TB0179D | C007 | 2 | | TB0179D | C008 | 2 | | 115-199 |
| 5982 | 24 | GK | | | 1-0 | 21-61-21 | TB0179A | C009 | 2 | | TB0179A | C008 | 2 | | 001-099 |
| 5982 | 24 | GK | | | 2-0 | 21-61-21 | TB0179D | C009 | 2 | | TB0179D | C008 | 2 | | 115-199 |
| 5983 | 22 | GK | | | 7-0 | 27-09-12 | D04676 | | 1 | | D41487J | 12 | | | 001-099 |
| 5983 | 22 | GK | | | 5-0 | 27-09-12 | D04676 | | 1 | | D41487J | 12 | | | 115-199 |
| 5984 | 22 | GK | | | 1-0 | 27-09-12 | D04676 | | 2 | | GD01703 | DC.. | 2 | | 001-099 |
| 5984 | 22 | GK | | | 4-0 | 27-09-12 | D04676 | | 2 | | GD01703 | DC.. | 2 | | 115-199 |
| 5985 | 22 | GK | | | 1-0 | 27-09-12 | D04674 | | 2 | | GD01703 | DC.. | 2 | | 001-099 |
| 5985 | 22 | GK | | | 4-0 | 27-09-12 | D04674 | | 2 | | GD01703 | DC.. | 2 | | 115-199 |
| 5986 | 22 | GK | | | 1-0 | 27-09-12 | D04674 | | 4 | | GD01703 | DC.. | 2 | | 001-099 |
| 5986 | 22 | GK | | | 4-0 | 27-09-12 | D04674 | | 4 | | GD01703 | DC.. | 2 | | 115-199 |
| 5987 | 22 | GK | | | 1-0 | 27-09-12 | D04674 | | 8 | | GD01703 | DC.. | 2 | | 001-099 |
| 5987 | 22 | GK | | | 4-0 | 27-09-12 | D04674 | | 8 | | GD01703 | DC.. | 2 | | 115-199 |
| 5988 | 22 | GK | | | 7-0 | 27-09-12 | D04674 | | 1 | | D41495J | 16 | | | 001-099 |
| 5988 | 22 | GK | | | 5-0 | 27-09-12 | D04674 | | 1 | | D41495J | 16 | | | 115-199 |
| 5989 | 22 | GK | | | 7-0 | 27-09-12 | D04674 | | 5 | | D41495J | 17 | | | 001-099 |
| 5989 | 22 | GK | | | 5-0 | 27-09-12 | D04674 | | 5 | | D41495J | 17 | | | 115-199 |
| 5990 | 22 | GK | | | 8-0 | 27-09-12 | D04674 | | 7 | | TB0178Y | C004 | BJ | | 001-099 |
| 5990 | 22 | GK | | | 4-0 | 27-09-12 | D04674 | | 7 | | TB0180Y | C002 | BJ | | 115-199 |
| 5991 | 22 | GK | | | 5-0 | 27-09-12 | D41495J | | 5 | | TB0178Y | C004 | BJ | | 001-099 |
| 5991 | 22 | GK | | | 6-0 | 27-09-12 | D41495J | | 5 | | TB0180Y | C002 | BJ | | 115-199 |
| 5992 | 22 | GK | | | 5-0 | 27-09-12 | D41495J | | 6 | | TB0178Y | C004 | BJ | | 001-099 |
| 5992 | 22 | GK | | | 6-0 | 27-09-12 | D41495J | | 6 | | TB0180Y | C002 | BJ | | 115-199 |
| 5993 | 22 | GK | | | 2-0 | 26-15-12 | D01870 | | 5 | | GD01703 | DC.. | 2 | | ALL |
| 5994 | 24 | GK | | | 8-0 | 26-15-12 | D01870 | | 3 | | D40570J | 21 | | | 001-099 |
| 5994 | 24 | GK | | | 9-0 | 26-15-12 | D01870 | | 3 | | D40570J | 21 | | | 115-199 |
| 5995 | 22 | GK | | | 3-0 | 32-09-12 | D03118 | | 6 | | TB0171Z | 4 | BJ | | 001-099 |
| 5995 | 22 | GK | | | 4-0 | 32-09-12 | D03118 | | 6 | | TB0180Z | 3 | BJ | | 115-199 |
| 5996 | 22 | GK | | | 3-0 | 32-09-12 | D03118 | | 12 | | TB0171Z | 5 | BJ | | 001-099 |
| 5996 | 22 | GK | | | 4-0 | 32-09-12 | D03118 | | 12 | | TB0180Z | 4 | BJ | | 115-199 |
| 5997 | 22 | GK | | | 8-0 | 32-42-12 | D03118 | | 7 | | D41748J | 20 | | | 001-099 |
| 5997 | 22 | GK | | | 5-0 | 32-42-12 | D03118 | | 7 | | D41546J | 48 | | | 115-199 |
| 5998 | 22 | GK | | | 8-0 | 32-42-12 | D03118 | | 14 | | D41748J | 21 | | | 001-099 |
| 5998 | 22 | GK | | | 5-0 | 32-42-12 | D03118 | | 14 | | D41546J | 37 | | | 115-199 |
| 6001 | 22 | GK | | | 3-0 | 32-09-12 | D04674 | | 12 | | TB0171Y | A001 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 50

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|------|---------|--------|----|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1270 | 286N1270 | | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 6001 | 22 | | GK | | 4-0 | 32-09-12 | | D04674 | | 12 | | | TB0180Y | A005 | BJ | | 115-199 |
| 6002 | 22 | | GK | | 3-0 | 32-09-12 | | D04676 | | 12 | | | TB0171Y | A001 | BJ | | 001-099 |
| 6002 | 22 | | GK | | 4-0 | 32-09-12 | | D04676 | | 12 | | | TB0180Y | A005 | BJ | | 115-199 |
| 6003 | 22 | | GK | | 3-0 | 32-09-12 | | D04674 | | 6 | | | TB0171Z | 4 | BJ | | 001-099 |
| 6003 | 22 | | GK | | 4-0 | 32-09-12 | | D04674 | | 6 | | | TB0180Z | 3 | BJ | | 115-199 |
| 6004 | 22 | | GK | | 3-0 | 32-09-12 | | D04676 | | 6 | | | TB0171Z | 4 | BJ | | 001-099 |
| 6004 | 22 | | GK | | 4-0 | 32-09-12 | | D04676 | | 6 | | | TB0180Z | 3 | BJ | | 115-199 |
| 6005 | 22 | | GK | | 7-0 | 32-09-12 | | D41616J | | 37 | | | TB0171Y | A001 | BJ | | 001-099 |
| 6005 | 22 | | GK | | 5-0 | 32-09-12 | | D41616J | | 37 | | | TB0180Y | A005 | BJ | | 115-199 |
| 6006 | 22 | | GK | | 3-0 | 32-09-12 | | TB0170Z | | 1 | BJ | | TB0171Y | A002 | BJ | | 001-099 |
| 6006 | 22 | | GK | | 3-0 | 32-09-12 | | TB0180Z | | 3 | BJ | | TB0171Z | 9 | BJ | | 115-199 |
| 6007 | 18 | | GK | | 7-0 | 21-44-11 | | D40184J | | 10 | | | TB0172G | 20 | 2 | | 001-099 |
| 6007 | 18 | | GK | | 9-0 | 21-44-11 | | D40184J | | 10 | | | TB0173F | A009 | 2 | | 115-199 |
| 6013 | 24 | | GK | | 8-0 | 21-58-21 | | D41032J | | 4 | | | TB0170A | A006 | 2 | *1 | ALL |
| 6014 | 24 | | GK | | 6-0 | 21-44-11 | | TB0173X | A007 | BJ | | | TB0172Z | 5 | BJ | | 115-199 |
| 6015 | 24 | | GK | | 4-0 | 21-44-11 | | TB0173A | C009 | 2 | * | | D07608 | A2 | | | 001-099 |
| 6015 | 24 | | GK | | 6-0 | 21-44-11 | | TB0173X | B007 | BJ | | | TB0172A | C001 | 2 | | 115-199 |
| 6018 | 24 | | GK | | 6-0 | 21-44-11 | | D02602 | X2 | | | | TB0173X | B008 | BJ | | 115-199 |
| 6019 | 24 | | GK | | 6-0 | 21-44-11 | | D41487J | 47 | | | | D07608 | A3 | | | 001-099 |
| 6019 | 24 | | GK | | 5-0 | 21-44-11 | | D41487J | 47 | | | | TB0173X | A008 | BJ | | 115-199 |
| 6020 | 24 | | GK | | 7-0 | 21-25-11 | | D41856J | 30 | | | | TB0177X | A012 | BJ | | ALL |
| 6022 | 24 | | GK | | 5-0 | 21-51-21 | | D40064J | 60 | | | | K00416 | 11 | C | | 001-099 |
| 6022 | 24 | | GK | | 6-0 | 21-51-21 | | D40064J | 60 | | | | K00416 | 11 | C | | 115-199 |
| 6023 | 24 | | GK | | 6-0 | 31-31-62 | | D04122 | 1 | | | | D41637J | 8 | | | 001-099 |
| 6023 | 22 | | GK | | 6-0 | 31-31-32 | | D04122 | 1 | | | | D41637J | 8 | | | 115-199 |
| 6024 | 24 | | GK | | 7-0 | 31-31-62 | | D04122 | 2 | | | | TB0178Y | A026 | BJ | | 001-099 |
| 6024 | 22 | | GK | | 7-0 | 31-31-32 | | D04122 | 2 | | | | TB0178Z | 26 | BJ | | 115-199 |
| 6025 | 24 | | GK | | 6-0 | 31-31-62 | | D04046 | 1 | | | | D41487J | 42 | | | 001-099 |
| 6025 | 22 | | GK | | 6-0 | 31-31-32 | | D04046 | 1 | | | | D41487J | 42 | | | 115-199 |
| 6026 | 24 | | GK | | 7-0 | 31-31-62 | | D04046 | 2 | | | | TB0178Y | A026 | BJ | | 001-099 |
| 6026 | 22 | | GK | | 7-0 | 31-31-32 | | D04046 | 2 | | | | TB0178Z | 26 | BJ | | 115-199 |
| 6029 | 22 | | GK | | 6-0 | 32-09-12 | | D04122 | 6 | | * | | TB0170Z | 1 | BJ | | 001-002 |
| 6029 | 22 | | GK | | 6-0 | 32-09-12 | | D04122 | 6 | | | | TB0170Z | 1 | BJ | | 003-099 |
| 6029 | 22 | | GK | | 4-0 | 32-09-12 | | D04122 | 6 | | | | TB0180Z | 3 | BJ | | 115-199 |
| 6030 | 22 | | GK | | 8-0 | 32-09-12 | | D04122 | 12 | | | | D41616J | 36 | | | 001-099 |
| 6030 | 22 | | GK | | 6-0 | 32-09-12 | | D04122 | 12 | | | | D41616J | 36 | | | 115-199 |
| 6031 | 22 | | GK | | 10-0 | 32-09-12 | | D04122 | 6 | | * | | D04046 | 6 | | | 001-002 |
| 6031 | 22 | | GK | | 10-0 | 32-09-12 | | D10750 | X1 | | * | | D04046 | 6 | | | 003-099 |
| 6031 | 22 | | GK | | 4-0 | 32-09-12 | | D04046 | 6 | | | | TB0180Z | 3 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 51

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 6032 | 22 | | GK | | 8-0 | 32-09-12 | D04046 | 12 | | | D41616J | 35 | | | 001-099 |
| 6032 | 22 | | GK | | 6-0 | 32-09-12 | D04046 | 12 | | | D41616J | 35 | | | 115-199 |
| 6036 | 22 | | GK | | 7-0 | 32-61-11 | TB0170Y | A003 | BJ | | D41739J | 44 | | | 001-099 |
| 6036 | 22 | | GK | | 7-0 | 32-61-11 | TB0170Y | A016 | BJ | | D41739J | 44 | | | 115-199 |
| 6038 | 20 | | GK | | 1-0 | 36-11-21 | D02484 | A2 | | | D02484 | X1 | | * | 001-099 |
| 6038 | 20 | | GK | | 4-0 | 36-11-21 | D02484 | A2 | | | TB0179Y | C011 | BJ | | 115-199 |
| 6039 | 20 | | GK | | 8-0 | 36-11-21 | D02486 | B2 | | | TB0178Z | 1 | BJ | | 001-099 |
| 6039 | 20 | | GK | | 10-0 | 36-11-21 | D02486 | B2 | | | TB0177Z | 9 | BJ | | 115-199 |
| 6041 | 20 | | GK | | 8-0 | 36-11-21 | D02486 | A2 | | | TB0178Z | 1 | BJ | | 001-099 |
| 6041 | 20 | | GK | | 10-0 | 36-11-21 | D02486 | A2 | | | TB0177Z | 9 | BJ | | 115-199 |
| 6042 | 20 | | GK | | 3-0 | 36-11-21 | D02482 | B2 | | | TB0179Z | 11 | BJ | | 001-099 |
| 6042 | 20 | | GK | | 10-0 | 36-11-21 | D02482 | B2 | | | TB0177Z | 10 | BJ | | 115-199 |
| 6043 | 20 | | GK | | 3-0 | 36-11-21 | D02482 | A2 | | | TB0179Z | 11 | BJ | | 001-099 |
| 6043 | 20 | | GK | | 10-0 | 36-11-21 | D02482 | A2 | | | TB0177Z | 10 | BJ | | 115-199 |
| 6044 | 22 | | GK | | 9-0 | 30-34-21 | D04090 | C1 | | | D41852J | 27 | | | ALL |
| 6045 | 20 | | GK | | 7-0 | 29-21-32 | D40718J | 39 | | | D05122 | A2 | | | 001-099 |
| 6045 | 20 | | GK | | 8-0 | 29-21-32 | D40718J | 39 | | | D05122 | A2 | | | 115-199 |
| 6046 | 20 | | GK | | 7-0 | 29-21-32 | D40718J | 12 | | | D05122 | X1 | | | 001-099 |
| 6046 | 20 | | GK | | 8-0 | 29-21-32 | D40718J | 12 | | | D05122 | X1 | | | 115-199 |
| 6047 | 20 | | GK | | 7-0 | 29-21-32 | D42062J | 3 | | | D05122 | A3 | | | 001-099 |
| 6047 | 20 | | GK | | 8-0 | 29-21-32 | D42062J | 3 | | | D05122 | A3 | | | 115-199 |
| 6048 | 20 | | GK | | 7-0 | 29-21-32 | D42062J | 5 | | | D05122 | A1 | | | 001-099 |
| 6048 | 20 | | GK | | 8-0 | 29-21-32 | D42062J | 5 | | | D05122 | A1 | | | 115-199 |
| 6049 | 22 | | GK | | 7-0 | 29-11-22 | D41030J | 31 | | | D05122 | C2 | | | 001-099 |
| 6049 | 22 | | GK | | 6-0 | 29-11-22 | D41030J | 31 | | | D05122 | C2 | | | 115-199 |
| 6050 | 22 | | GK | | 7-0 | 29-11-22 | D41030J | 32 | | | D05122 | C1 | | | 001-099 |
| 6050 | 22 | | GK | | 6-0 | 29-11-22 | D41030J | 32 | | | D05122 | C1 | | | 115-199 |
| 6051 | 22 | | GK | | 7-0 | 32-42-11 | D41739J | 43 | | | D05122 | D1 | | | ALL |
| 6052 | 22 | | GK | | 7-0 | 32-42-11 | D41739J | 41 | | | D05122 | D2 | | | ALL |
| 6053 | 22 | | GK | | 7-0 | 32-42-11 | D41739J | 42 | | | D05122 | D3 | | | ALL |
| 6054 | 20 | | GK | | 2-0 | 29-21-32 | D05122 | X2 | | | GD01705 | DC.. | 2 | | 001-099 |
| 6054 | 20 | | GK | | 4-0 | 29-21-32 | D05122 | X2 | | | GD01705 | DC.. | 2 | | 115-199 |
| 6055 | 20 | | GK | | 6-0 | 36-11-21 | D40594J | 13 | | | TB0178Z | 1 | BJ | | 001-099 |
| 6055 | 20 | | GK | | 5-0 | 36-11-21 | D40594J | 13 | | | TB0177Z | 9 | BJ | | 115-199 |
| 6056 | 20 | | GK | | 7-0 | 36-11-21 | TB0178Y | A019 | BJ | | TB0177Z | 9 | BJ | | 115-199 |
| 6057 | 22 | | GK | | 9-0 | 30-34-21 | D04090 | C2 | | | D41852J | 28 | | | ALL |
| 6064 | 20 | | GK | | 6-0 | 36-11-21 | D41856J | 36 | | | TB0178Z | 1 | BJ | | 001-099 |
| 6064 | 20 | | GK | | 6-0 | 36-11-21 | D41856J | 36 | | | TB0177Z | 9 | BJ | | 115-199 |
| 6065 | 20 | | GK | | 3-0 | 36-11-21 | D02482 | X1 | | | TB0179Z | 11 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 52

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 6065 | 20 | | GK | | 10-0 | 36-11-21 | D02482 | | X1 | | TB0177Z | 10 | BJ | | 115-199 |
| 6066 | 20 | | GK | | 7-0 | 36-11-21 | D02482 | | A3 | | D40064J | 33 | | | ALL |
| 6067 | 20 | | GK | | 3-0 | 36-11-21 | D02482 | | X2 | | GD01705 | DC.. | 2 | | ALL |
| 6068 | 20 | | GK | | 7-0 | 36-11-21 | D02486 | | X2 | | D42010J | 35 | | | 001-099 |
| 6068 | 20 | | GK | | 7-0 | 36-11-21 | D02486 | | X2 | | D42010J | 16 | | | 115-199 |
| 6069 | 22 | | GK | | 9-0 | 30-34-21 | D04090 | | C3 | | D41852J | 29 | | | ALL |
| 6070 | 20 | | GK | | 1-0 | 36-11-21 | D02484 | | B2 | * | D02484 | X1 | | * | 001-099 |
| 6070 | 20 | | GK | | 4-0 | 36-11-21 | TB0179Y | C011 | BJ | | D02484 | X1 | | | 115-199 |
| 6071 | 20 | | GK | | 3-0 | 36-11-21 | D02484 | | X2 | | GD01705 | DC.. | 2 | | 001-099 |
| 6071 | 20 | | GK | | 4-0 | 36-11-21 | D02484 | | X2 | | GD01705 | DC.. | 2 | | 115-199 |
| 6072 | 20 | | GK | | 7-0 | 36-11-21 | D02484 | | A3 | | D40064J | 34 | | | ALL |
| 6073 | 20 | | GK | | 3-0 | 36-11-21 | D02486 | | X1 | | D05208 | X1 | | * | 001-099 |
| 6073 | 20 | | GK | | 4-0 | 36-11-21 | D02486 | | X1 | | TB0179Y | A012 | BJ | | 115-199 |
| 6074 | 20 | | GK | | 7-0 | 36-11-22 | D02482 | | B3 | | D40064J | 12 | | | ALL |
| 6075 | 20 | | GK | | 7-0 | 36-11-22 | D02484 | | B3 | | D40064J | 46 | | | ALL |
| 6076 | 20 | | GK | | 3-0 | 36-11-21 | D02484 | | B2 | * | D05208 | A3 | | | 001-099 |
| 6076 | 20 | | GK | | 4-0 | 36-11-21 | D02484 | | B2 | | TB0179Y | C011 | BJ | | 115-199 |
| 6077 | 20 | | GK | | 4-0 | 36-11-21 | D05208 | | A3 | | TB0179Y | C011 | BJ | | 115-199 |
| 6078 | 20 | | GK | | 3-0 | 36-11-21 | D02486 | | B3 | | TB0179Z | 11 | BJ | | 001-099 |
| 6078 | 20 | | GK | | 10-0 | 36-11-21 | D02486 | | B3 | | TB0177Z | 10 | BJ | | 115-199 |
| 6079 | 20 | | GK | | 1-0 | 36-11-21 | D05208 | | X1 | * | D05208 | B2 | | * | 001-099 |
| 6079 | 20 | | GK | | 4-0 | 36-11-21 | D05208 | | X1 | | TB0179Y | A012 | BJ | | 115-199 |
| 6080 | 20 | | GK | | 3-0 | 36-11-21 | D05208 | | X2 | | TB0179A | A001 | 2 | | 001-099 |
| 6080 | 20 | | GK | | 10-0 | 36-11-21 | D05208 | | X2 | | TB0177A | A011 | 2 | | 115-199 |
| 6081 | 20 | | GK | | 7-0 | 36-11-21 | D05208 | | B2 | * | D41856J | 35 | | | 001-099 |
| 6081 | 20 | | GK | | 4-0 | 36-11-21 | D05208 | | B2 | | TB0179Y | A012 | BJ | | 115-199 |
| 6082 | 20 | | GK | | 3-0 | 36-11-21 | D05208 | | C2 | | TB0179A | A001 | 2 | | 001-099 |
| 6082 | 20 | | GK | | 10-0 | 36-11-21 | D05208 | | C2 | | TB0177A | A011 | 2 | | 115-199 |
| 6085 | 20 | | GK | | 3-0 | 36-11-21 | D05208 | | B1 | | TB0179Z | 11 | BJ | | 001-099 |
| 6085 | 20 | | GK | | 10-0 | 36-11-21 | D05208 | | B1 | | TB0177Z | 10 | BJ | | 115-199 |
| 6086 | 20 | | GK | | 3-0 | 36-11-21 | D05208 | | C1 | | GD01705 | DC.. | 2 | | 001-099 |
| 6086 | 20 | | GK | | 4-0 | 36-11-21 | D05208 | | C1 | | GD01705 | DC.. | 2 | | 115-199 |
| 6087 | 20 | | GK | | 3-0 | 36-11-21 | D05208 | | A2 | | D02486 | A1 | | | 001-099 |
| 6087 | 20 | | GK | | 4-0 | 36-11-21 | D05208 | | A2 | | D02486 | A1 | | | 115-199 |
| 6088 | 24 | | GK | | 7-0 | 36-22-11 | TB0179A | C001 | 2 | | D40064J | 40 | | | 001-099 |
| 6088 | 24 | | GK | | 7-0 | 36-22-11 | TB0177A | C011 | 2 | | D40064J | 40 | | | 115-199 |
| 6089 | 20 | | GK | | 7-0 | 36-11-21 | TB0179Y | A012 | BJ | | D41856J | 35 | | | 115-199 |
| 6090 | 24 | | GK | | 7-0 | 30-31-11 | D00618 | | B2 | | D41030J | 3 | | | 001-099 |
| 6090 | 24 | | GK | | 6-0 | 30-31-11 | D00618 | | B2 | | D41030J | 3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 53

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 6091 | 24 | | GK | | 3-0 | 30-31-11 | D00618 | | B1 | | D04090 | D1 | | * | 001-099 |
| 6091 | 24 | | GK | | 4-0 | 30-31-11 | D00618 | | B1 | | TB0171Y | C004 | BJ | | 115-199 |
| 6092 | 20 | | GK | | 10-0 | 30-34-22 | D00634 | | A2 | | D04244 | C2 | | * | 001-099 |
| 6092 | 18 | | GK | | 8-0 | 30-34-22 | D00634 | | A2 | | TB0178G | 2 | 2 | | 115-199 |
| 6093 | 24 | | GK | | 7-0 | 30-31-11 | D04090 | | D1 | * | D41030J | 4 | | | 001-099 |
| 6093 | 24 | | GK | | 4-0 | 30-31-11 | D04090 | | D1 | | TB0171Y | C004 | BJ | | 115-199 |
| 6094 | 24 | | GK | | 7-0 | 30-31-11 | D04090 | | D2 | | D41030J | 10 | | | 001-099 |
| 6094 | 24 | | GK | | 6-0 | 30-31-11 | D04090 | | D2 | | D41030J | 10 | | | 115-199 |
| 6095 | 20 | | GK | | 10-0 | 30-34-22 | D00634 | | A3 | | D04244 | C1 | | * | 001-099 |
| 6095 | 18 | | GK | | 8-0 | 30-34-22 | D00634 | | A3 | | TB0178G | 1 | 2 | | 115-199 |
| 6100 | 20 | | GK | | 8-0 | 36-11-21 | D05260 | | X1 | | TB0178Z | 1 | BJ | | 001-009 |
| 6100 | 20 | | GK | | 10-0 | 36-11-21 | D05260 | | X1 | | TB0178Z | 1 | BJ | | 010-099 |
| 6100 | 20 | | GK | | 10-0 | 36-11-21 | D05260 | | X1 | | TB0177Z | 9 | BJ | | 115-199 |
| 6101 | 24 | | GK | | 9-0 | 36-11-41 | D05260 | | B3 | | TB0178X | A029 | BJ | | 115-199 |
| 6102 | 24 | | GK | | 3-0 | 36-11-41 | D05260 | | B2 | | GD01706 | DC.. | 2 | | 001-099 |
| 6102 | 24 | | GK | | 4-0 | 36-11-41 | D05260 | | B2 | | GD01702 | DC.. | 2 | | 115-199 |
| 6103 | 24 | | GK | | 3-0 | 36-11-21 | D05260 | | A2 | | GD01706 | DC.. | 2 | | 001-099 |
| 6103 | 24 | | GK | | 4-0 | 36-11-21 | D05260 | | A2 | | GD01702 | DC.. | 2 | | 115-199 |
| 6104 | 24 | | GK | | 7-0 | 36-11-21 | D05260 | | A1 | | D41856J | 37 | | | 001-099 |
| 6104 | 24 | | GK | | 9-0 | 36-11-21 | D05260 | | A1 | | TB0178Y | C019 | BJ | | 115-199 |
| 6105 | 20 | | GK | | 7-0 | 36-11-21 | D05260 | | X2 | | D40064J | 35 | | | ALL |
| 6106 | 24 | | GK | | 7-0 | 73-21-21 | D05246 | | 13 | | D42010J | 22 | | | 001-099 |
| 6106 | 24 | | GK | | 6-0 | 73-21-21 | D05246 | | 13 | | D42010J | 22 | | | 115-199 |
| 6107 | 24 | | GK | | 7-0 | 73-21-21 | D05246 | | 1 | | D42010J | 21 | | | 001-099 |
| 6107 | 24 | | GK | | 6-0 | 73-21-21 | D05246 | | 1 | | D42010J | 21 | | | 115-199 |
| 6108 | 24 | | GK | | 7-0 | 73-21-22 | D05246 | | 9 | | D42010J | 25 | | | 001-099 |
| 6108 | 24 | | GK | | 6-0 | 73-21-22 | D05246 | | 9 | | D42010J | 25 | | | 115-199 |
| 6109 | 24 | | GK | | 7-0 | 73-21-22 | D05246 | | 11 | | D42010J | 26 | | | 001-099 |
| 6109 | 24 | | GK | | 6-0 | 73-21-22 | D05246 | | 11 | | D42010J | 26 | | | 115-199 |
| 6110 | 24 | | GK | | 7-0 | 73-21-22 | D05246 | | 14 | | D41998J | 8 | | | 001-099 |
| 6110 | 24 | | GK | | 9-0 | 73-21-22 | D05246 | | 14 | | D41998J | 8 | | | 115-199 |
| 6111 | 24 | | GK | | 10-0 | 73-21-22 | D05246 | | 7 | | D07008 | C1 | | * | 001-099 |
| 6111 | 24 | | GK | | 12-0 | 73-21-22 | D05246 | | 7 | | D07008 | C1 | | * | 115-199 |
| 6112 | 24 | | GK | | 7-0 | 73-21-22 | D05246 | | 3 | | D42010J | 28 | | | 001-099 |
| 6112 | 24 | | GK | | 6-0 | 73-21-22 | D05246 | | 3 | | D42010J | 28 | | | 115-199 |
| 6113 | 24 | | GK | | 3-0 | 73-21-22 | D05246 | | 5 | | GD01703 | DC.. | 2 | | 001-099 |
| 6113 | 24 | | GK | | 4-0 | 73-21-22 | D05246 | | 5 | | GD01703 | DC.. | 2 | | 115-199 |
| 6114 | 22 | | GK | | 3-0 | 77-12-42 | D05246 | | 12 | | GD01703 | DC.. | 2 | | 001-099 |
| 6114 | 20 | | GK | | 4-0 | 77-12-42 | D05246 | | 12 | | GD01703 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 54

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 6115 | 22 | | GK | | 8-0 | 77-12-42 | D05246 | | 6 | | TB0173Y | C005 | BJ | | 001-099 |
| 6115 | 22 | | GK | | 9-0 | 77-12-42 | D05246 | | 6 | | TB0178Y | C037 | BJ | | 115-199 |
| 6130 | 24 | | GK | | 8-0 | 36-11-41 | D01864 | | 5 | | TB0173Y | C006 | BJ | | 001-099 |
| 6130 | 24 | | GK | | 10-0 | 36-11-41 | D01864 | | 5 | | TB0177Y | C008 | BJ | | 115-199 |
| 6132 | 24 | | GK | | 8-0 | 36-11-41 | TB0173Y | A005 | BJ | | D01864 | 3 | | | 001-099 |
| 6132 | 24 | | GK | | 10-0 | 36-11-41 | TB0177Y | A008 | BJ | | D01864 | 3 | | | 115-199 |
| 6201 | 22 | | GK | | 9-0 | 76-11-21 | D01510 | | B2 | | TB0177X | D004 | BJ | | 001-099 |
| 6201 | 22 | | GK | | 10-0 | 76-11-21 | TB0177X | D004 | BJ | | D01510 | B2 | | | 115-199 |
| 6202 | 22 | | GK | | 7-0 | 76-11-21 | D01510 | | B3 | | D41616J | 7 | | | ALL |
| 6299 | 20 | | GK | | 5-0 | 29-21-31 | D41034J | | 12 | | D40738J | 21 | | | 001-099 |
| 6299 | 20 | | GK | | 4-0 | 29-21-31 | D40738J | | 21 | | D41034J | 12 | | | 115-199 |
| 6300 | 20 | | GK | | 9-0 | 24-51-61 | D00622 | | 1 | | D40978J | 17 | | | ALL |
| 6301 | 20 | | GK | | 2-0 | 24-51-61 | D00622 | | 2 | | GD01701 | DC.. | 2 | | 001-099 |
| 6301 | 20 | | GK | | 4-0 | 24-51-61 | D00622 | | 2 | | GD01705 | DC.. | 2 | | 115-199 |
| 6302 | 22 | | GK | | 8-0 | 30-21-11 | D41994J | | 26 | | TB0179A | C016 | 2 | | ALL |
| 6303 | 22 | | GK | | 14-0 | 30-21-11 | D06324 | | 8 | | TB0179Y | A006 | BJ | | 001-099 |
| 6303 | 22 | | GK | | 11-0 | 30-21-11 | D06324 | | 8 | | TB0179Y | A011 | BJ | | 115-199 |
| 6304 | 20 | | GK | | 8-0 | 23-32-02 | D01603 | | A1 | | TB0177X | A014 | BJ | | 001-099 |
| 6304 | 20 | | GK | | 10-0 | 23-32-02 | D01603 | | A1 | | TB0177X | A014 | BJ | | 115-199 |
| 6306 | 20 | | GK | | 8-0 | 23-32-02 | D01603 | | A2 | | D41909J | 1 | | | 001-099 |
| 6306 | 20 | | GK | | 10-0 | 23-32-02 | D01603 | | A2 | | D41909J | 1 | | | 115-199 |
| 6310 | 22 | | GK | | 14-0 | 30-21-11 | D06324 | | 3 | | D01508 | X1 | | * | 001-099 |
| 6310 | 22 | | GK | | 11-0 | 30-21-11 | D01508 | | X1 | * | D06324 | 3 | | | 115-199 |
| 6311 | 22 | | GK | | 6-0 | 30-21-11 | D06324 | | 6 | | GD01714 | DC.. | 2 | | ALL |
| 6338 | 24 | | GK | | 8-0 | 31-31-62 | D01872 | | 7 | | D41739J | 21 | | | 001-099 |
| 6339 | 24 | | GK | | 7-0 | 31-31-62 | D01872 | | 14 | | TB0178Y | A026 | BJ | | 001-099 |
| 6342 | 22 | | GK | | 5-0 | 31-31-01 | D41739J | | 6 | | TB0178Y | A039 | BJ | | 001-099 |
| 6346 | 24 | | PK | | 7-0 | 34-61-26 | D02277 | | 7 | | D43017J | 2 | | | 115-199 |
| 6347 | 24 | | PK | | 7-0 | 34-61-26 | D02277 | | 3 | | D43017J | 1 | | | 115-199 |
| 6349 | 24 | | PK | | 7-0 | 34-61-26 | D02281 | | 7 | | D43017J | 18 | | | 115-199 |
| 6350 | 24 | | PK | | 7-0 | 34-61-26 | D02281 | | 3 | | D43017J | 19 | | | 115-199 |
| 6351 | 24 | | PK | | 7-0 | 34-61-26 | D02283 | | 7 | | D43017J | 29 | | | 115-199 |
| 6352 | 24 | | PK | | 7-0 | 34-61-26 | D02283 | | 3 | | D43017J | 30 | | | 115-199 |
| 6356 | 20 | | GK | | 8-0 | 23-32-02 | D01603 | | A3 | | TB0177X | B014 | BJ | | 001-099 |
| 6356 | 20 | | GK | | 10-0 | 23-32-02 | D01603 | | A3 | | TB0177X | B014 | BJ | | 115-199 |
| 6357 | 20 | | GK | | 8-0 | 23-32-02 | D01603 | | B1 | | TB0177X | C014 | BJ | | 001-099 |
| 6357 | 20 | | GK | | 10-0 | 23-32-02 | D01603 | | B1 | | TB0177X | C014 | BJ | | 115-199 |
| 6385 | 20 | | GK | | 8-0 | 23-32-02 | D01603 | | B2 | | D41909J | 2 | | | 001-099 |
| 6385 | 20 | | GK | | 10-0 | 23-32-02 | D01603 | | B2 | | D41909J | 2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 55

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1270
Page 56
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 6464 | 20 | | GK | | 6-0 | 38-13-11 | D40496J | | 21 | | D41032J | 5 | | | 001-099 |
| 6465 | 22 | | GA | | 3-0 | 34-25-12 | D01923 | | X1 | | TB0179A | C015 | 2 | | 002 |
| 6466 | 22 | | GA | | 6-0 | 34-25-12 | D01923 | | X2 | | D41487J | 50 | | | 002 |
| 6483 | 20 | | GK | | 2-0 | 21-45-11 | D00620 | | B3 | | GD01705 | AC.. | 2 | | 003-009 |
| 6504 | 22 | | GK | | 5-0 | 32-61-11 | D07750 | | A1 | | SM00045 | | WI | | 001-002, 115-199 |
| 6504 | 22 | | GK | | 5-0 | 32-61-11 | D07750 | | A1 | | TB0171Z | 15 | BJ | | 003-099 |
| 6505 | 22 | | GK | | 5-0 | 32-61-11 | D07750 | | A2 | | SM00062 | | W | | 001-002 |
| 6505 | 22 | | GK | | 5-0 | 32-61-11 | D07750 | | A2 | | TB0171Z | 14 | BJ | | 003-099 |
| 6505 | 22 | | GK | | 3-0 | 32-61-11 | D07750 | | A2 | | SM00062 | | W | | 115-199 |
| 6506 | 22 | | GK | | 5-0 | 32-61-11 | D07750 | | A3 | | D41032J | 10 | | | 001-002 |
| 6506 | 22 | | GK | | 10-0 | 32-61-11 | D07750 | | A3 | | D41034J | 31 | | | 003-099 |
| 6506 | 22 | | GK | | 3-0 | 32-61-11 | D07750 | | A3 | | D41032J | 10 | | | 115-199 |
| 6508 | 22 | | GK | | 5-0 | 32-61-11 | D41030J | | 54 | | SM00062 | | W | | 001-002, 115-199 |
| 6508 | 22 | | GK | | 10-0 | 32-61-11 | TB0171Z | | 14 | BJ | D41034J | 26 | | | 003-099 |
| 6509 | 22 | | GK | | 5-0 | 32-61-11 | D07750 | | X1 | | SM00045 | | WI | | 001-002 |
| 6509 | 22 | | GK | | 5-0 | 32-61-11 | D07750 | | X1 | | TB0171Z | 15 | BJ | | 003-099 |
| 6509 | 22 | | GK | | 4-0 | 32-61-11 | D07750 | | X1 | | SM00045 | | WI | | 115-199 |
| 6510 | 22 | | GK | | 5-0 | 32-61-11 | D07750 | | X2 | | GD01703 | DC.. | 2 | | 001-099 |
| 6510 | 22 | | GK | | 4-0 | 32-61-11 | D07750 | | X2 | | GD01703 | DC.. | 2 | | 115-199 |
| 6511 | 24 | | GK | | 5-0 | 78-36-21 | D07720 | | 3 | | SM00014 | | WI | | 001-002 |
| 6511 | 24 | | GK | | 9-0 | 78-36-21 | D07720 | | 3 | | SM00014 | | WI | | 003-099 |
| 6511 | 24 | | GK | | 4-0 | 78-36-21 | D07720 | | 3 | | SM00014 | | WI | | 115-199 |
| 6512 | 24 | | GK | | 5-0 | 78-36-21 | D07720 | | 7 | | TB0178Y | A029 | BJ | | 001-002 |
| 6512 | 24 | | GK | | 9-0 | 78-36-21 | D07720 | | 7 | | SM00013 | | WI | | 003-099 |
| 6512 | 24 | | GK | | 8-0 | 78-36-21 | D07720 | | 7 | | TB0174Y | A006 | BJ | | 115-199 |
| 6519 | 20 | | GK | | 4-0 | 28-22-32 | D41860J | | 15 | | D41994J | 48 | | | 009-099 |
| 6520 | 20 | | GK | | 4-0 | 28-22-32 | D41860J | | 17 | | D41994J | 49 | | | 009-099 |
| 6521 | 20 | | GK | | 4-0 | 28-22-32 | D41860J | | 18 | | D41994J | 50 | | | 009-099 |
| 6522 | 24 | | GK | | 5-0 | 78-36-21 | SM00014 | | | WI | D41478J | 22 | | | 001-002, 115-199 |
| 6522 | 24 | | GK | | 3-0 | 78-36-21 | SM00014 | | | WI | D41478J | 22 | | | 003-099 |
| 6523 | 24 | | GK | | 5-0 | 78-36-21 | D07720 | | 5 | | SM00014 | | WI | | 001-002, 115-199 |
| 6523 | 24 | | GK | | 9-0 | 78-36-21 | D07720 | | 5 | | SM00014 | | WI | | 003-099 |
| 6524 | 22 | | GK | | 5-0 | 32-61-11 | SM00045 | | | WI | D41030J | 55 | | | 001-002, 115-199 |
| 6524 | 22 | | GK | | 10-0 | 32-61-11 | TB0171Z | | 15 | BJ | D41034J | 27 | | | 003-099 |
| 6533 | 22 | | GK | | 3-0 | 78-34-21 | M10010 | | B | C | TB0178Z | 2 | BJ | | 001-002 |
| 6533 | 22 | | GK | | 5-0 | 78-34-21 | TB0174Y | | C019 | BJ | M10010 | | B | C | 003-099 |
| 6533 | 22 | | GK | | 3-0 | 78-34-21 | TB0174Y | | C005 | BJ | M10010 | | B | C | 115-199 |
| 6534 | 22 | | GK | | 5-0 | 78-34-21 | D41478J | | 18 | | GD03701 | ST.. | 2 | | 001-002 |
| 6534 | 22 | | GK | | 3-0 | 78-34-21 | D41478J | | 18 | | GD03701 | ST.. | 2 | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 57

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|-------------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | | |
| 6534 | 22 | | GK | | 2-0 | 78-34-21 | D41478J | | 18 | | | GD03701 | ST.. | 2 | | 115-199 |
| 6535 | 22 | | GK | | 5-0 | 78-34-21 | D07768 | | A3 | | | D41858J | 13 | | | 001-002, 115-199 |
| 6535 | 22 | | GK | | 9-0 | 78-34-21 | D07768 | | A3 | | | D41858J | 11 | | | 003-099 |
| 6536 | 22 | | GK | | 5-0 | 78-34-21 | D07768 | | A2 | | | D42010J | 13 | | | 001-002 |
| 6536 | 22 | | GK | | 9-0 | 78-34-21 | D07768 | | A2 | | | D42010J | 41 | | | 003-099 |
| 6536 | 22 | | GK | | 6-0 | 78-34-21 | D07768 | | A2 | | | D42010J | 13 | | | 115-199 |
| 6537 | 22 | | GK | | 5-0 | 78-34-21 | D07768 | | X1 | * | | D07768 | A1 | | | 001-002 |
| 6537 | 22 | | GK | | 1-0 | 78-34-21 | D07768 | | A1 | | | D07768 | X1 | | * | 003-099, 115-199 |
| 6538 | 22 | | GK | | 5-0 | 78-34-21 | D07768 | | X1 | * | | D41860J | 30 | | | 001-002 |
| 6538 | 22 | | GK | | 10-0 | 78-34-21 | D07768 | | X1 | * | | D42176J | 19 | | | 003-099 |
| 6538 | 22 | | GK | | 6-0 | 78-34-21 | D07768 | | X1 | * | | D41860J | 30 | | | 115-199 |
| 6539 | 22 | | GK | | 5-0 | 78-34-21 | D07768 | | X2 | | | GD01703 | DC.. | 2 | | 001-002 |
| 6539 | 22 | | GK | | 5-0 | 78-34-21 | D07768 | | X2 | | | GD03447 | DC.. | 2 | | 003-099 |
| 6539 | 22 | | GK | | 3-0 | 78-34-21 | D07768 | | X2 | | | GD01703 | DC.. | 2 | | 115-199 |
| 6540 | 22 | | GA | | 8-0 | 31-31-41 | D04015 | | 3 | | | D41909J | 4 | | | 010-099 |
| 6541 | 18 | | GK | | 5-0 | 78-34-61 | D07766 | | A3 | | | D41478J | 19 | 18 | | 001-002 |
| 6541 | 18 | | GK | | 9-0 | 78-34-61 | D41478J | | 19 | 18 | | D07766 | A3 | | | 003-099 |
| 6541 | 18 | | GK | | 5-0 | 78-34-61 | D41478J | | 19 | 18 | | D07766 | A3 | | | 115-199 |
| 6542 | 18 | | GK | | 5-0 | 78-34-61 | D07766 | | A1 | | | SM00060 | | WI | | 001-002 |
| 6542 | 18 | | GK | | 5-0 | 78-34-61 | D07766 | | A1 | | | TB0180G | 9 | 2 | | 003-099 |
| 6542 | 18 | | GK | | 4-0 | 78-34-61 | D07766 | | A1 | | | SM00060 | | W | | 115-199 |
| 6543 | 18 | | GK | | 5-0 | 78-34-61 | D07766 | | X1 | | | SM00060 | | WI | | 001-002 |
| 6543 | 18 | | GK | | 5-0 | 78-34-61 | D07766 | | X1 | | | TB0180G | 9 | 2 | | 003-099 |
| 6543 | 18 | | GK | | 4-0 | 78-34-61 | D07766 | | X1 | | | SM00060 | | W | | 115-199 |
| 6544 | 18 | | GK | | 5-0 | 78-34-61 | D07766 | | X2 | | | GD01706 | DC.. | 2 | | 001-002 |
| 6544 | 18 | | GK | | 5-0 | 78-34-61 | D07766 | | X2 | | | GD03447 | DC.. | 2 | | 003-099 |
| 6544 | 18 | | GK | | 2-0 | 78-34-61 | D07766 | | X2 | | | GD01706 | DC.. | 2 | | 115-199 |
| 6545 | 18 | | GK | | 5-0 | 78-34-61 | D07766 | | A2 | | | SM00015 | | WI | | 001-002 |
| 6545 | 18 | | GK | | 9-0 | 78-34-61 | D07766 | | A2 | | | SM00015 | | WI | | 003-099 |
| 6545 | 18 | | GK | | 4-0 | 78-34-61 | D07766 | | A2 | | | SM00015 | | WI | | 115-199 |
| 6546 | 20 | | GK | | 5-0 | 78-34-61 | SM00015 | | | WI | | D42010J | 5 | | | 001-002 |
| 6546 | 20 | | GK | | 3-0 | 78-34-61 | D42010J | | 5 | | | SM00015 | | WI | | 003-099 |
| 6546 | 20 | | GK | | 3-0 | 78-34-61 | SM00015 | | | WI | | D42010J | 5 | | | 115-199 |
| 6547 | 20 | | GA | | 5-0 | 78-34-61 | SM00015 | | | WI | | D01864 | 7 | | | 001-002, 115-199 |
| 6547 | 20 | | GK | | 9-0 | 78-34-61 | D01864 | | 7 | | | SM00015 | | WI | | 003-099 |
| 6548 | 20 | | GK | | 5-0 | 78-34-61 | D07778 | | X2 | | | GD01706 | DC.. | 2 | | 001-002 |
| 6548 | 20 | | GK | | 5-0 | 78-34-61 | D07778 | | X2 | | | GD03447 | DC.. | 2 | | 003-099 |
| 6548 | 20 | | GK | | 4-0 | 78-34-61 | D07778 | | X2 | | | GD01706 | DC.. | 2 | | 115-199 |
| 6549 | 20 | | GK | | 5-0 | 78-34-61 | TB0180A | | A006 | 2 | | GD01706 | DC.. | 2 | | 001-002 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 58

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 6549 | 20 | | GK | | 5-0 | 78-34-61 | TB0180A | A006 | 2 | | GD03447 | DC.. | 2 | | 003-099 |
| 6549 | 20 | | GK | | 2-0 | 78-34-61 | TB0180A | A006 | 2 | | GD01706 | DC.. | 2 | | 115-199 |
| 6550 | 24 | | GK | | 5-0 | 78-36-21 | D07720 | | 2 | | D41994J | | 9 | | 001-002 |
| 6550 | 24 | | GK | | 10-0 | 78-36-21 | D07720 | | 2 | | D41994J | | 9 | | 003-099 |
| 6550 | 24 | | GK | | 6-0 | 78-36-21 | D07720 | | 2 | | D41994J | | 9 | | 115-199 |
| 6551 | 22 | | GK | | 5-0 | 78-34-21 | D41478J | | 17 | | M10010 | A | C | | 001-002 |
| 6551 | 22 | | GK | | 6-0 | 78-34-21 | D41478J | | 17 | | M10010 | A | C | | 115-199 |
| 6558 | 24 | | GK | | 4-0 | 36-11-41 | D01600 | | 6 | | D07038 | A2 | | | 010-099 |
| 6560 | 22 | | GK | | 10-0 | 76-11-12 | D02216 | | 3 | | SM00051 | | WI | | 001-099 |
| 6560 | 22 | | GK | | 4-0 | 76-11-12 | D02216 | | 3 | | SM00051 | | WI | | 115-199 |
| 6561 | 22 | | GK | | 4-0 | 76-11-12 | D02216 | | 8 | | SM00049 | | WI | | 115-199 |
| 6562 | 22 | | GK | | 4-0 | 76-11-12 | D02220 | | 3 | | SM00049 | | WI | | 115-199 |
| 6563 | 22 | | GK | | 10-0 | 76-11-12 | SM00051 | | | WI | D41258J | | 4 | | 001-099 |
| 6563 | 22 | | GK | | 6-0 | 76-11-12 | D41258J | | 4 | | SM00051 | | WI | | 115-199 |
| 6564 | 24 | | GK | | 10-0 | 78-36-21 | D41994J | | 31 | | D02640 | B2 | | * | 001-003 |
| 6564 | 24 | | GK | | 10-0 | 78-36-21 | D41994J | | 41 | | D02640 | B2 | | * | 004-099, 115-199 |
| 6565 | 24 | | GK | | 16-0 | 78-36-21 | D02640 | | B2 | * | D01870 | | 9 | | ALL |
| 6566 | 24 | | GK | | 16-0 | 78-36-21 | D02640 | | B3 | | D01870 | | 10 | | ALL |
| 6567 | 24 | | GK | | 10-0 | 78-36-21 | D01870 | | 11 | | D41994J | | 16 | | 001-099 |
| 6567 | 24 | | GK | | 10-0 | 78-36-21 | D01870 | | 11 | | D41994J | | 29 | | 115-199 |
| 6571 | 22 | | GA | | 6-0 | 31-31-41 | D04015 | | 7 | | TB0173A | C007 | 2 | | 010-099 |
| 6572 | 22 | | GA | | 6-0 | 31-31-41 | TB0173A | A007 | 2 | | TB0170Y | C004 | BJ | | 010-099 |
| 6760 | 20 | | GK | | 10-0 | 27-62-11 | D00630 | | 14 | | TB0173Y | A020 | BJ | | ALL |
| 6764 | 24 | | GK | | 4-0 | 76-11-12 | TB0178Y | C027 | BJ | | TB0174B | A025 | 2 | | 001-099 |
| 6765 | 24 | | GK | | 4-0 | 76-11-12 | TB0174Y | A005 | BJ | | TB0174B | A025 | 2 | | 115-199 |
| 6768 | 24 | | GK | | 4-0 | 76-11-12 | TB0174B | C025 | 2 | | GD01714 | DC.. | 2 | | ALL |
| 6784 | 20 | | GK | | 9-0 | 27-62-11 | D41766J | | 7 | | TB0173Y | A020 | BJ | | ALL |
| 6785 | 20 | | GK | | 4-0 | 27-62-11 | D04199 | | A2 | | TB0173Y | A019 | BJ | | ALL |
| 6786 | 20 | | GK | | 10-0 | 27-62-11 | D04199 | | A1 | | TB0173Y | A002 | BJ | | 001-099 |
| 6786 | 20 | | GK | | 10-0 | 27-62-11 | D04199 | | A1 | | TB0178Y | A024 | BJ | | 115-199 |
| 6787 | 20 | | GK | | 4-0 | 27-62-11 | D04199 | | X1 | | TB0173Y | C019 | BJ | | ALL |
| 6829 | 20 | | GK | | 9-0 | 27-62-11 | D42062J | | 6 | | GD01711 | DC.. | 2 | | ALL |
| 6830 | 20 | | GK | | 10-0 | 32-09-12 | D04199 | | C1 | | TB0171Z | | 6 | BJ | 001-099 |
| 6830 | 20 | | GK | | 10-0 | 32-09-12 | D04199 | | C1 | | TB0171Z | | 7 | BJ | 115-199 |
| 6833 | 20 | | GK | | 10-0 | 32-09-12 | D04199 | | C2 | | D10750 | | X2 | | ALL |
| 6834 | 20 | | GK | | 9-0 | 27-62-11 | D42062J | | 11 | | GD01711 | ST.. | 2 | | ALL |
| 6837 | 20 | | GK | | 7-0 | 27-62-11 | D41030J | | 17 | | TB0173Y | C019 | BJ | | ALL |
| 6838 | 20 | | GK | | 6-0 | 27-62-11 | D42062J | | 13 | | TB0173Y | C019 | BJ | | ALL |
| 6839 | 20 | | GK | | 6-0 | 27-62-11 | D42062J | | 14 | | D04199 | | X2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 59

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| 8000 | 24 | | GK | | 7-0 | 34-22-19 | D41739J | | 17 | | D00610 | | 5 | | 001-099 |
| 8001 | 22 | | GK | | 4-0 | 34-22-19 | D00610 | | 4 | | GD01702 | DC.. | 2 | | 001-099 |
| 8003 | 22 | | GA | | 6-4 | 34-43-14 | D01864 | | 9 | | D41487J | | 48 | | 002 |
| 8004 | 22 | | GA | | 6-4 | 34-43-14 | D01864 | | 11 | | GD03447 | DC.. | 2 | | 002 |
| 8005 | 18 | | GK | | 5-0 | 28-22-11 | TB0178G | | 18 | 2 | D41856J | | 45 | 18 | 003-099 |
| 8006 | 18 | | GK | | 5-0 | 28-22-11 | TB0178G | | 19 | 2 | D41856J | | 46 | 18 | 003-099 |
| 8090 | 22 | | GA | | 0-7 | 31-31-41 | TB0170Y | A004 | BJ | | TB0170Y | C004 | BJ | | 010-099 |
| 8117 | 20 | | GA | | 10-0 | 28-22-11 | D11710 | | A2 | | D40594J | | 46 | | 001-099 |
| 8117 | 20 | | GA | | 6-0 | 28-22-11 | D11710 | | A2 | | D40594J | | 46 | | 115-199 |
| 8119 | 20 | | GA | | 6-8 | 28-22-11 | D11712 | | A2 | | SM00016 | | | WI | ALL |
| 8120 | 20 | | GA | | 5-0 | 28-22-11 | TB0178G | | 19 | 2 | SM00016 | | | WI | 001-099 |
| 8120 | 20 | | GA | | 4-0 | 28-22-11 | TB0178G | | 31 | 2 | SM00016 | | | WI | 115-199 |
| 8127 | 20 | | GA | | 9-2 | 28-22-11 | D11712 | | X2 | | TB0178D | A037 | 2 | | 001-099 |
| 8127 | 20 | | GA | | 9-2 | 28-22-11 | D11712 | | X2 | | TB0178D | A033 | 2 | | 115-199 |
| 8128 | 20 | | GA | | 5-0 | 28-22-11 | TB0178D | C037 | 2 | | D41860J | | 21 | | 001-099 |
| 8128 | 20 | | GA | | 6-0 | 28-22-11 | TB0178D | C033 | 2 | | D41860J | | 21 | | 115-199 |
| 8129 | 20 | | GA | | 5-0 | 28-22-11 | TB0178D | A037 | 2 | | D41495J | | 30 | | 001-099 |
| 8129 | 20 | | GA | | 5-0 | 28-22-11 | TB0178D | A033 | 2 | | D41495J | | 30 | | 115-199 |
| 8131 | 20 | | GA | | 6-0 | 28-22-11 | D11712 | | X1 | | D11710 | | A1 | | 001-099 |
| 8131 | 20 | | GA | | 5-0 | 28-22-11 | D11712 | | X1 | | D11710 | | A1 | | 115-199 |
| 8132 | 20 | | GA | | 9-0 | 28-22-11 | SM00016 | | | WI | D11710 | | X1 | | ALL |
| 8133 | 20 | | GA | | 5-0 | 28-22-11 | D11710 | | X2 | | GD01710 | AC.. | 2 | | ALL |
| 8135 | 20 | | GA | | 5-0 | 28-22-11 | K10012 | | X1 | C | D11712 | | A3 | | ALL |
| 8136 | 20 | | PA | | 7-0 | 28-22-11 | D40594J | | 55 | | D11712 | | B2 | | ALL |
| 8137 | 20 | | PA | | 4-0 | 28-22-11 | D11712 | | B3 | | K10874 | | X1 | C | ALL |
| 8138 | 20 | | PA | | 8-0 | 28-22-11 | K10874 | | X2 | C | GD01705 | AC.. | 2 | | ALL |
| 8503 | 22 | | GK | | 6-0 | 27-23-11 | D41616J | | 24 | | D42176J | | 25 | | 001-099 |
| 8504 | 22 | | GK | | 6-0 | 27-23-11 | D00616 | | C3 | * | D41616J | | 25 | | 001-099 |
| 8505 | 22 | | GK | | 8-0 | 27-23-11 | D00616 | | C3 | * | D42176J | | 12 | | 001-099 |
| 8512 | 18 | | GK | | 4-0 | 30-34-22 | D40718J | | 35 | 18 | TB0178G | | 2 | 2 | 115-199 |
| 8514 | 18 | | GK | | 4-0 | 30-34-22 | D42008J | | 17 | 18 | TB0178G | | 1 | 2 | 115-199 |
| 8518 | 22 | | GK | | 5-0 | 30-34-22 | D41909J | | 45 | | D42176J | | 27 | | ALL |
| 8901 | 20 | | GK | | 0-18 | 30-34-22 | D42008J | | 19 | | GD03700 | ST.. | 2 | | 001-099 |
| 8901 | 20 | | GK | | 3-0 | 30-34-22 | D42008J | | 19 | | GD03701 | ST.. | 2 | | 115-199 |
| B-01 | | | | | 0-0 | 21-44-11 | TS5044 | | 1 | | TB0173X | A007 | BJ | | 115-199 |
| B-02 | | | | | 0-0 | 21-44-11 | TS5044 | | 2 | | GD01710 | DC.. | 2 | | 115-199 |
| B-03 | | | | | 0-0 | 21-44-11 | TS5044 | | 3 | | TB0173X | A008 | BJ | | 115-199 |
| B-04 | | | | | 0-0 | 21-44-11 | TS5044 | | 4 | | TB0173X | B007 | BJ | | 115-199 |
| B-05 | | | | | 0-0 | 21-44-11 | TS5044 | | 5 | | TB0173X | B008 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 60

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1270 | 286N1270 | | | INTERNAL P37- PLATES (A,B,C,E,F) (continued) | | | | | | | | | | | |
| FRAA | | | | | 0-0 | 31-31-42 | D01809 | | | AA | GD01710 | ST.. | 2 | | 001-099 |
| FRAG | | | | | 0-0 | 78-34-61 | D41478J | | | AG | D41478J | 6 | | | ALL |
| PA01 | | | | | 0-0 | 38-15-11 | D00060 | G2 | | | D00060 | G3 | | | 001-099 |
| PB01 | | | | | 0-0 | 38-15-11 | D00060 | G1 | | | D00060 | G3 | | | 115-199 |
| W1272 | 286N1272 | | | P37 MODULE WIRING, CB PANEL | | | | | | | | | | | |
| 0001 | 08 | | HA | | 4-1 | 24-51-52 | TB5070 | 9 | E | | C01218 | =B | D | | 001-099 |
| 0001 | 08 | | HA | | 4-4 | 24-51-52 | K00102 | C2 | F | | C01218 | =B | D | | 115-199 |
| 0002 | 08 | | HA | | 3-9 | 24-51-52 | TB5070 | 8 | E | | C03008 | B2 | D | * | 001-099 |
| 0002 | 08 | | HA | | 4-2 | 24-51-52 | K00102 | B2 | F | | C03008 | B2 | D | * | 115-199 |
| 0003 | 08 | | HA | | 3-9 | 24-51-52 | TB5070 | 7 | E | | C03008 | A2 | D | * | 001-099 |
| 0003 | 08 | | HA | | 4-2 | 24-51-52 | K00102 | A2 | F | | C03008 | A2 | D | * | 115-199 |
| 0004 | 12 | | HA | | 3-0 | 24-51-52 | C03008 | A2 | D | * | C00333 | A2 | D | | 001-099 |
| 0004 | 12 | | HA | | 2-11 | 24-51-52 | C03008 | A2 | D | * | C00333 | A2 | D | | 115-199 |
| 0005 | 12 | | HA | | 3-1 | 24-51-52 | C03008 | B2 | D | * | C00333 | B2 | D | | 001-099 |
| 0005 | 12 | | HA | | 3-0 | 24-51-52 | C03008 | B2 | D | * | C00333 | B2 | D | | 115-199 |
| 0006 | 12 | | HA | | 3-3 | 24-51-52 | C03008 | C2 | D | * | C00333 | C2 | D | | 001-099 |
| 0006 | 12 | | HA | | 3-2 | 24-51-52 | C03008 | C2 | D | * | C00333 | C2 | D | | 115-199 |
| 0014 | 12 | | HA | | 1-5 | 24-51-52 | C00301 | A2 | D | | C00302 | A2 | D | * | 001-099 |
| 0015 | 12 | | HA | | 1-5 | 24-51-52 | C00301 | B2 | D | | C00302 | B2 | D | | 001-099 |
| 0016 | 12 | | HA | | 1-4 | 24-51-52 | C00301 | C2 | D | | C00302 | C2 | D | | 001-099 |
| 0016 | 22 | | GA | | 7-1 | 23-34-15 | C04403 | =L | D | | D41739J | 23 | | | 115-199 |
| 0017 | 14 | | GA | | 3-0 | 24-51-24 | C04074 | =B | D | * | C04403 | =B | D | * | 001-099 |
| 0017 | 14 | | HA | | 2-5 | 24-51-24 | C04074 | =B | D | * | C04403 | =B | D | * | 115-199 |
| 0018 | 22 | | GA | | 8-0 | 23-34-15 | C04403 | =L | D | | D41739J | 23 | | | 001-099 |
| 0020 | 08 | | HA | | 2-2 | 24-51-52 | C03008 | C2 | D | * | C01219 | =B | D | | 001-099 |
| 0020 | 08 | | HA | | 2-6 | 24-51-52 | C03008 | C2 | D | * | C01219 | =B | D | | 115-199 |
| 0021 | 12 | | HA | | 2-5 | 24-51-52 | C03008 | A1 | D | | C01232 | =B | D | | 001-099 |
| 0021 | 12 | | HA | | 2-4 | 24-51-52 | C03008 | A1 | D | | C01232 | =B | D | | 115-199 |
| 0022 | 12 | | HA | | 2-1 | 24-51-52 | C01255 | =B | D | | C00630 | =B | D | * | 001-008, 115-199 |
| 0022 | 12 | | HA | | 1-6 | 24-51-52 | C01255 | =B | D | | C04262 | =B | D | | 009-099 |
| 0023 | 12 | | HA | | 2-7 | 24-51-52 | C00630 | =B | D | * | C04169 | =B | D | * | 115-199 |
| 0024 | 12 | | HA | | 2-9 | 24-51-52 | C04169 | =B | D | | C01224 | =B | D | | 001-099 |
| 0024 | 12 | | HA | | 2-9 | 24-51-52 | C04169 | =B | D | * | C01224 | =B | D | | 115-199 |
| 0025 | 12 | | HA | | 3-0 | 24-51-52 | C03008 | B1 | D | | C01142 | =B | D | | ALL |
| 0026 | 12 | | HA | | 3-0 | 24-51-52 | C03008 | C1 | D | | C01150 | =B | D | * | 001-099 |
| 0026 | 12 | | HA | | 2-11 | 24-51-52 | C03008 | C1 | D | | C01150 | =B | D | * | 115-199 |
| 0027 | 20 | | GA | | 7-0 | 28-21-11 | C00075 | =B | D | | TB0177X | C012 | BJ | | 001-099 |
| 0028 | 16 | | GA | | 3-0 | 21-25-11 | C00337 | C2 | D | * | C04374 | =B | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 61

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1272 | | 286N1272 | | | | P37 MODULE WIRING, CB PANEL (continued) | | | | | | | | | |
| 0028 | 16 | GA | | | 2-10 | 21-25-11 | C00337 | C2 | D | * | C04374 | =B | D | | 115-199 |
| 0029 | 24 | GK | | | 7-0 | 21-25-11 | C04374 | =L | D | | TB0177X | A012 | BJ | | 001-099 |
| 0029 | 24 | GK | | | 5-3 | 21-25-11 | C04374 | =L | D | | TB0177X | A012 | BJ | | 115-199 |
| 0030 | 10 | HA | | | 3-7 | 24-51-24 | K00120 | C2 | E | | C00337 | C1 | D | * | 001-099 |
| 0030 | 10 | HA | | | 3-3 | 24-51-24 | K00120 | C2 | E | | C00337 | C1 | D | * | 115-199 |
| 0031 | 10 | HA | | | 3-5 | 24-51-24 | K00120 | B2 | E | | C00337 | B1 | D | * | 001-099 |
| 0031 | 10 | HA | | | 3-2 | 24-51-24 | K00120 | B2 | E | | C00337 | B1 | D | * | 115-199 |
| 0032 | 10 | HA | | | 3-4 | 24-51-24 | K00120 | A2 | E | | C00337 | A1 | D | * | 001-099 |
| 0032 | 10 | HA | | | 3-0 | 24-51-24 | K00120 | A2 | E | | C00337 | A1 | D | * | 115-199 |
| 0033 | 12 | HA | | | 2-9 | 24-51-24 | C00337 | C1 | D | * | C03010 | C1 | D | * | 001-099 |
| 0033 | 10 | HA | | | 1-11 | 24-51-24 | C00337 | C1 | D | * | C04075 | =B | D | | 115-199 |
| 0034 | 14 | GA | | | 2-0 | 24-51-24 | C04076 | =B | D | | C00699 | =B | D | | 001-099 |
| 0034 | 14 | GA | | | 1-7 | 24-51-24 | C04076 | =B | D | | C00699 | =B | D | | 115-199 |
| 0036 | 12 | GA | | | 1-5 | 24-51-24 | C04028 | =B | D | | C03010 | C1 | D | * | 001-099 |
| 0036 | 14 | GA | | | 1-7 | 24-51-24 | C04028 | =B | D | | C03010 | C1 | D | * | 115-199 |
| 0040 | 12 | HA | | | 2-7 | 24-51-24 | C00337 | B1 | D | * | C03010 | B1 | D | * | 001-099 |
| 0040 | 10 | HA | | | 1-10 | 24-51-24 | C00337 | B1 | D | * | C04074 | =B | D | * | 115-199 |
| 0041 | 14 | GA | | | 2-0 | 24-51-24 | C04074 | =B | D | * | C00700 | =B | D | | 001-099 |
| 0041 | 14 | GA | | | 1-7 | 24-51-24 | C04074 | =B | D | * | C00700 | =B | D | | 115-199 |
| 0042 | 14 | GA | | | 1-0 | 24-51-24 | C01265 | =B | D | * | C01264 | =B | D | * | ALL |
| 0043 | 12 | GA | | | 1-4 | 24-51-24 | C04135 | =B | D | | C03010 | B1 | D | * | 001-099 |
| 0043 | 14 | GA | | | 1-7 | 24-51-24 | C04135 | =B | D | | C03010 | B1 | D | | 115-199 |
| 0045 | 12 | HA | | | 2-3 | 24-51-52 | C01150 | =B | D | * | C01217 | =B | D | | 001-099 |
| 0045 | 12 | HA | | | 2-3 | 24-51-52 | C01217 | =B | D | | C01150 | =B | D | * | 115-199 |
| 0050 | 12 | HA | | | 2-5 | 24-51-24 | C00337 | A1 | D | * | C03010 | A1 | D | * | 001-099 |
| 0050 | 10 | HA | | | 1-11 | 24-51-24 | C00337 | A1 | D | * | C01264 | =B | D | * | 115-199 |
| 0051 | 14 | GA | | | 2-0 | 24-51-24 | C01264 | =B | D | * | C04073 | =B | D | * | 001-099 |
| 0051 | 14 | GA | | | 1-3 | 24-51-24 | C01264 | =B | D | * | C04073 | =B | D | * | 115-199 |
| 0052 | 14 | GA | | | 2-0 | 24-51-24 | C04073 | =B | D | * | C04134 | =B | D | * | 001-099 |
| 0052 | 14 | GA | | | 1-3 | 24-51-24 | C04073 | =B | D | * | C04134 | =B | D | * | 115-199 |
| 0053 | 12 | HA | | | 1-2 | 24-51-24 | C04134 | =B | D | * | C03010 | A1 | D | * | 001-099 |
| 0053 | 14 | GA | | | 1-5 | 24-51-24 | C04134 | =B | D | * | C03010 | A1 | D | | 115-199 |
| 0057 | 08 | HA | | | 0-10 | 24-51-24 | C03023 | A1 | D | * | C03046 | A1 | D | | 001-099 |
| 0058 | 08 | HA | | | 0-10 | 24-51-24 | C03023 | B1 | D | * | C03046 | B1 | D | | 001-099 |
| 0059 | 08 | HA | | | 0-10 | 24-51-24 | C03023 | C1 | D | * | C03046 | C1 | D | | 001-099 |
| 0060 | 12 | HA | | | 4-1 | 24-51-21 | TB5070 | 4 | E | | C00392 | A1 | D | * | 001-099 |
| 0060 | 12 | HA | | | 4-0 | 24-51-21 | TB5070 | 4 | E | | C00392 | A1 | D | * | 115-199 |
| 0061 | 12 | HA | | | 4-1 | 24-51-21 | TB5070 | 5 | E | | C00392 | B1 | D | * | 001-099 |
| 0061 | 12 | HA | | | 4-1 | 24-51-21 | TB5070 | 5 | E | | C00392 | B1 | D | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 62

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1272 | 286N1272 | | | P37 MODULE WIRING, CB PANEL (continued) | | | | | | | | | | | |
| 0062 | 12 | | HA | | 4-1 | 24-51-21 | TB5070 | 6 | E | | C00392 | C1 | D | * | 001-099 |
| 0062 | 12 | | HA | | 4-1 | 24-51-21 | TB5070 | 6 | E | | C00392 | C1 | D | | 115-199 |
| 0063 | 12 | | HA | | 2-1 | 24-51-21 | C00392 | A1 | D | * | C01124 | =B | D | | 001-099 |
| 0063 | 12 | | HA | | 2-0 | 24-51-21 | C00392 | A1 | D | * | C01124 | =B | D | | 115-199 |
| 0065 | 12 | | GA | | 2-3 | 24-51-24 | C04426 | =B | D | | C04361 | =B | D | * | 001-099 |
| 0070 | 22 | | GA | | 3-0 | 24-51-52 | L00373 | 1 | C | | C00302 | A2 | D | * | 001-099 |
| 0070 | 22 | | GA | | 2-11 | 24-51-52 | L00373 | 1 | C | | C00302 | A2 | D | | 115-199 |
| 0071 | 22 | | GA | | 5-0 | 24-51-52 | L00373 | 2 | C | | GD01717 | AC.. | F | | 001-099 |
| 0071 | 20 | | GA | | 5-0 | 24-51-52 | L00373 | 2 | C | | GD01717 | AC.. | F | | 115-199 |
| 0072 | 06 | | CQ | | 1-6 | 24-53-51 | T00126 | GND | E | | GD01717 | AC.. | F | | 115-199 |
| 0075 | 12 | | HA | | 2-3 | 24-51-24 | C04403 | =B | D | * | C04362 | =B | D | | ALL |
| 0076 | 12 | | HA | | 2-4 | 24-51-24 | C04075 | =B | D | | C04361 | =B | D | * | 001-099 |
| 0076 | 12 | | HA | | 1-6 | 24-51-24 | C03010 | C1 | D | * | C04361 | =B | D | | 115-199 |
| 0077 | 14 | | GA | | 3-0 | 24-51-24 | C01265 | =B | D | * | C04363 | =B | D | | 001-099 |
| 0077 | 14 | | GA | | 2-8 | 24-51-24 | C01265 | =B | D | * | C04363 | =B | D | | 115-199 |
| 0078 | 12 | | HA | | 2-9 | 24-51-21 | C01126 | =B | D | | C04442 | =B | D | | 001-099 |
| 0078 | 12 | | HA | | 2-5 | 24-51-21 | C01126 | =B | D | | C04442 | =B | D | | 115-199 |
| 0079 | 12 | | HA | | 3-3 | 24-51-21 | C00392 | B1 | D | * | C04441 | =B | D | | 001-099 |
| 0079 | 12 | | HA | | 3-1 | 24-51-21 | C00392 | B1 | D | | C04441 | =B | D | | 115-199 |
| 0080 | 12 | | HA | | 3-3 | 24-51-21 | C00392 | C1 | D | * | C04440 | =B | D | | 001-099 |
| 0080 | 12 | | HA | | 3-1 | 24-51-21 | C00392 | C1 | D | | C04440 | =B | D | | 115-199 |
| 0081 | 20 | | GA | | 7-0 | 23-32-02 | C04440 | =L | D | | TB0177X | A014 | BJ | | 001-099 |
| 0081 | 20 | | GA | | 6-3 | 23-32-02 | C04440 | =L | D | | TB0177X | A014 | BJ | | 115-199 |
| 0082 | 20 | | GA | | 7-0 | 23-32-02 | C04361 | =L | D | | TB0177X | B014 | BJ | | 001-099 |
| 0082 | 20 | | GA | | 6-0 | 23-32-02 | C04361 | =L | D | | TB0177X | B014 | BJ | | 115-199 |
| 0083 | 20 | | GA | | 7-0 | 23-32-02 | C04441 | =L | D | | TB0177X | C014 | BJ | | 001-099 |
| 0083 | 20 | | GA | | 6-4 | 23-32-02 | C04441 | =L | D | | TB0177X | C014 | BJ | | 115-199 |
| 0084 | 20 | | GA | | 7-0 | 23-32-02 | C04362 | =L | D | | TB0177X | D014 | BJ | | 001-099 |
| 0084 | 20 | | GA | | 6-1 | 23-32-02 | C04362 | =L | D | | TB0177X | D014 | BJ | | 115-199 |
| 0085 | 20 | | GA | | 7-0 | 23-32-02 | C04442 | =L | D | | TB0177X | A015 | BJ | | 001-099 |
| 0085 | 20 | | GA | | 6-4 | 23-32-02 | C04442 | =L | D | | TB0177X | A015 | BJ | | 115-199 |
| 0086 | 20 | | GA | | 7-0 | 23-32-02 | C04363 | =L | D | | TB0177X | B015 | BJ | | 001-099 |
| 0086 | 20 | | GA | | 6-2 | 23-32-02 | C04363 | =L | D | | TB0177X | B015 | BJ | | 115-199 |
| 0087 | 22 | | GA | | 8-0 | 23-34-15 | C04426 | =L | D | | D41739J | 49 | | | 001-099 |
| 0090 | 20 | | GA | | 7-0 | 28-21-11 | C00075 | =L | D | | TB0177X | B012 | BJ | | 001-099 |
| 0093 | 24 | | GK | | 3-0 | 24-27-21 | D41748J | 14 | | | D42176J | 11 | | | ALL |
| 0094 | 10 | | HA | | 4-5 | 25-31-13 | TB5070 | 1 | E | | C03023 | A2 | D | | 001-099 |
| 0095 | 10 | | HA | | 4-5 | 25-31-13 | TB5070 | 2 | E | | C03023 | B2 | D | | 001-099 |
| 0096 | 10 | | HA | | 4-5 | 25-31-13 | TB5070 | 3 | E | | C03023 | C2 | D | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 63

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1272 | 286N1272 | | | P37 MODULE WIRING, CB PANEL (continued) | | | | | | | | | | | |
| 0100 | 20 | | GK | | 5-5 | 33-22-11 | D40718J | | 42 | | C04285 | =L | D | | 115-199 |
| 0101 | 08 | | HA | | 3-6 | 24-51-24 | K10298 | | A2 | E | C03013 | A2 | D | | 115-199 |
| 0102 | 08 | | HA | | 3-8 | 24-51-24 | K10298 | | B2 | E | C03013 | B2 | D | | 115-199 |
| 0103 | 08 | | HA | | 3-9 | 24-51-24 | K10298 | | C2 | E | C03013 | C2 | D | | 115-199 |
| 0201 | 20 | | GA | | 7-0 | 24-31-11 | C00301 | | A1 | D | D40912J | 22 | | | 001-099 |
| 0201 | 20 | | GA | | 6-3 | 24-31-11 | C00301 | | A1 | D | D40912J | 22 | | | 115-199 |
| 0202 | 20 | | GA | | 7-0 | 24-31-11 | C00301 | | B1 | D | D40912J | 23 | | | 001-099 |
| 0202 | 20 | | GA | | 6-4 | 24-31-11 | C00301 | | B1 | D | D40912J | 23 | | | 115-199 |
| 0203 | 20 | | GA | | 7-0 | 24-31-11 | C00301 | | C1 | D | D40912J | 24 | | | 001-099 |
| 0203 | 20 | | GA | | 6-5 | 24-31-11 | C00301 | | C1 | D | D40912J | 24 | | | 115-199 |
| 0204 | 18 | | GA | | 7-0 | 24-31-41 | C00302 | | A1 | D | D41082J | 4 | | | 001-099 |
| 0204 | 18 | | GA | | 6-0 | 24-31-41 | C00302 | | A1 | D | D41082J | 4 | | | 115-199 |
| 0205 | 18 | | GA | | 7-0 | 24-31-41 | C00302 | | B1 | D | D41082J | 5 | | | 001-099 |
| 0205 | 18 | | GA | | 6-1 | 24-31-41 | C00302 | | B1 | D | D41082J | 5 | | | 115-199 |
| 0206 | 18 | | GA | | 7-0 | 24-31-41 | C00302 | | C1 | D | D41082J | 6 | | | 001-099 |
| 0206 | 18 | | GA | | 6-2 | 24-31-41 | C00302 | | C1 | D | D41082J | 6 | | | 115-199 |
| 0207 | 18 | | GA | | 6-0 | 21-58-21 | C00333 | | A1 | D | TB0177F | A001 | 2 | | 001-099 |
| 0207 | 18 | | GA | | 5-1 | 21-58-21 | C00333 | | A1 | D | TB0177F | A001 | 2 | | 115-199 |
| 0208 | 18 | | GA | | 6-0 | 21-58-21 | C00333 | | B1 | D | TB0177F | C001 | 2 | | 001-099 |
| 0208 | 18 | | GA | | 5-2 | 21-58-21 | C00333 | | B1 | D | TB0177F | C001 | 2 | | 115-199 |
| 0209 | 18 | | GA | | 6-0 | 21-58-21 | C00333 | | C1 | D | TB0177F | A002 | 2 | | 001-099 |
| 0209 | 18 | | GA | | 5-3 | 21-58-21 | C00333 | | C1 | D | TB0177F | A002 | 2 | | 115-199 |
| 0210 | 14 | | GA | | 5-0 | 21-25-11 | C00337 | | A2 | D | K00416 | A1 | E | | 001-099 |
| 0210 | 14 | | GA | | 4-2 | 21-25-11 | C00337 | | A2 | D | K00416 | A1 | E | | 115-199 |
| 0211 | 14 | | GA | | 5-0 | 21-25-11 | C00337 | | B2 | D | K00416 | B1 | E | | 001-099 |
| 0211 | 14 | | GA | | 4-3 | 21-25-11 | C00337 | | B2 | D | K00416 | B1 | E | | 115-199 |
| 0212 | 14 | | GA | | 5-0 | 21-25-11 | C00337 | | C2 | D | K00416 | C1 | E | | 001-099 |
| 0212 | 14 | | GA | | 4-4 | 21-25-11 | C00337 | | C2 | D | K00416 | C1 | E | | 115-199 |
| 0213 | 20 | | GA | | 5-0 | 30-41-12 | C01124 | | =L | D | D41122J | 1 | | | 001-099 |
| 0213 | 18 | | GA | | 4-7 | 30-41-12 | C01124 | | =L | D | D41122J | 1 | | | 115-199 |
| 0214 | 20 | | GA | | 5-0 | 30-41-12 | C01126 | | =L | D | D41122J | 2 | | | 001-099 |
| 0214 | 18 | | GA | | 4-8 | 30-41-12 | C01126 | | =L | D | D41122J | 2 | | | 115-199 |
| 0215 | 22 | | GA | | 8-0 | 34-61-15 | C00630 | | =L | D | D41487J | 1 | | | 001-008 |
| 0215 | 22 | | GA | | 7-2 | 34-61-15 | C00630 | | =L | D | D41487J | 1 | | | 115-199 |
| 0216 | 20 | | GA | | 5-0 | 21-45-11 | C00699 | | =L | D | TB0177Y | C005 | BJ | | 001-099 |
| 0216 | 20 | | GA | | 6-6 | 21-45-11 | C00699 | | =L | D | TB0178Y | C004 | BJ | | 115-199 |
| 0217 | 20 | | GA | | 6-0 | 21-45-11 | C00700 | | =L | D | D41856J | 5 | | | ALL |
| 0218 | 14 | | GA | | 6-0 | 24-53-51 | C00871 | | =L | D | D40496J | 24 | | | 001-099 |
| 0218 | 14 | | GA | | 5-2 | 24-53-51 | C00871 | | =L | D | T00126 | HV | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 64

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1272 | 286N1272 | | | | P37 MODULE WIRING, CB PANEL (continued) | | | | | | | | | | | | |
| 0219 | 20 | | GA | | 6-0 | 30-71-11 | C01142 | =L | D | | | TB0177X | A004 | BJ | | 001-099 | |
| 0219 | 20 | | GA | | 6-8 | 30-71-11 | C01142 | =L | D | | | TB0178G | 13 | 2 | | 115-199 | |
| 0220 | 20 | | GA | | 7-0 | 30-71-21 | C01149 | =L | D | | | D40050J | 6 | | | 001-099 | |
| 0220 | 24 | | GK | | 6-8 | 30-71-21 | C01149 | =L | D | | | D40064J | 44 | | | 115-199 | |
| 0221 | 20 | | GA | | 6-0 | 30-71-21 | C01150 | =L | D | | | D40184J | 3 | | | 001-099 | |
| 0221 | 24 | | GK | | 5-2 | 30-71-21 | C01150 | =L | D | | | D40184J | 3 | | | 115-199 | |
| 0222 | 24 | | GK | | 7-0 | 33-21-11 | C01217 | =L | D | | | D40718J | 44 | | | 001-099 | |
| 0222 | 24 | | GK | | 6-1 | 33-21-11 | C01217 | =L | D | | | D40718J | 44 | | | 115-199 | |
| 0223 | 16 | | GA | | 5-0 | 33-21-11 | C01218 | =L | D | | | D41408J | 33 | | | 001-099 | |
| 0223 | 16 | | GA | | 5-1 | 33-21-11 | C01218 | =L | D | | | D41408J | 33 | | | 115-199 | |
| 0224 | 16 | | GA | | 6-0 | 33-21-11 | C01219 | =L | D | | | D41408J | 32 | | | 001-099 | |
| 0224 | 16 | | GA | | 5-2 | 33-21-11 | C01219 | =L | D | | | D41408J | 32 | | | 115-199 | |
| 0225 | 24 | | GK | | 6-0 | 33-21-31 | C01224 | =L | D | | | D40718J | 54 | | | 001-099 | |
| 0225 | 24 | | GK | | 5-3 | 33-21-31 | C01224 | =L | D | | | D40718J | 54 | | | 115-199 | |
| 0226 | 16 | | GA | | 5-0 | 33-21-31 | C01264 | =L | D | | | D41408J | 39 | | | 001-099 | |
| 0226 | 16 | | GA | | 4-9 | 33-21-31 | C01264 | =L | D | | | D41408J | 39 | | | 115-199 | |
| 0227 | 16 | | GA | | 5-0 | 33-21-31 | C01265 | =L | D | | | D41408J | 38 | | | 001-099 | |
| 0227 | 16 | | GA | | 4-10 | 33-21-31 | C01265 | =L | D | | | D41408J | 38 | | | 115-199 | |
| 0228 | 22 | | GA | | 6-0 | 33-26-11 | C01232 | =L | D | * | | D41302J | 4 | | | 001-099 | |
| 0228 | 20 | | GA | | 5-1 | 33-26-11 | C01232 | =L | D | * | | D41302J | 4 | | | 115-199 | |
| 0229 | 22 | | GA | | 5-0 | 33-26-11 | C01232 | =L | D | * | | D40496J | 7 | | | 001-099 | |
| 0229 | 20 | | GA | | 5-1 | 33-26-11 | C01232 | =L | D | * | | D40496J | 7 | | | 115-199 | |
| 0230 | 22 | | GA | | 6-0 | 33-22-11 | C01255 | =L | D | | | D40718J | 52 | | | 001-099 | |
| 0230 | 22 | | GA | | 6-6 | 33-22-11 | C01255 | =L | D | | | TB0178Z | 18 | BJ | | 115-199 | |
| 0234 | 18 | | GA | | 6-0 | 21-44-11 | C03010 | A2 | D | | | TB0177F | C002 | 2 | | 001-099 | |
| 0234 | 18 | | GA | | 6-10 | 21-44-11 | C03010 | A2 | D | | | TB0178F | A008 | 2 | | 115-199 | |
| 0235 | 18 | | GA | | 6-0 | 21-44-11 | C03010 | B2 | D | | | TB0177F | C007 | 2 | | 001-099 | |
| 0235 | 18 | | GA | | 6-10 | 21-44-11 | C03010 | B2 | D | | | TB0178F | C007 | 2 | | 115-199 | |
| 0236 | 18 | | GA | | 6-0 | 21-44-11 | C03010 | C2 | D | | | TB0177F | A007 | 2 | | 001-099 | |
| 0236 | 18 | | GA | | 6-11 | 21-44-11 | C03010 | C2 | D | | | TB0178F | A007 | 2 | | 115-199 | |
| 0237 | 22 | | GA | | 4-10 | 21-58-24 | C03029 | A1 | D | | | TB0177X | A003 | BJ | | 115-199 | |
| 0238 | 22 | | GA | | 4-10 | 21-58-24 | C03029 | B1 | D | | | TB0177X | B003 | BJ | | 115-199 | |
| 0239 | 22 | | GA | | 4-11 | 21-58-24 | C03029 | C1 | D | | | TB0177X | C003 | BJ | | 115-199 | |
| 0240 | 22 | | GA | | 7-0 | 23-31-19 | C04028 | =L | D | | | D41739J | 16 | | | 001-099 | |
| 0240 | 22 | | GA | | 6-4 | 23-34-15 | C04028 | =L | D | | | D41739J | 16 | | | 115-199 | |
| 0241 | 18 | | GA | | 7-0 | 25-29-11 | C04042 | =L | D | | | D40718J | 55 | 18 | | 001-099 | |
| 0241 | 18 | | GA | | 6-1 | 25-29-11 | C04042 | =L | D | | | D40760J | 3 | | | 115-199 | |
| 0242 | 18 | | GA | | 6-0 | 25-29-11 | C04247 | =L | D | | | D41748J | 28 | | | 001-099 | |
| 0242 | 18 | | GA | | 5-5 | 25-29-11 | C04247 | =L | D | | | D41748J | 28 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 65

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1272 | | 286N1272 | | | | P37 MODULE WIRING, CB PANEL (continued) | | | | | | | | | |
| 0243 | 20 | GA | | | 5-0 | 33-23-21 | C04073 | =L | D | | D40410J | 25 | | | 001-099 |
| 0243 | 20 | GA | | | 4-10 | 33-23-21 | C04073 | =L | D | | D40410J | 25 | | | 115-199 |
| 0244 | 20 | GA | | | 5-0 | 33-23-22 | C04074 | =L | D | | D40410J | 26 | | | ALL |
| 0245 | 20 | GA | | | 5-0 | 33-23-23 | C04075 | =L | D | | D40410J | 27 | | | 001-099 |
| 0245 | 20 | GA | | | 5-1 | 33-23-23 | C04075 | =L | D | | D40410J | 27 | | | 115-199 |
| 0246 | 20 | GA | | | 5-0 | 33-23-24 | C04076 | =L | D | | D40410J | 28 | | | 001-099 |
| 0246 | 20 | GA | | | 4-11 | 33-23-24 | C04076 | =L | D | | D40410J | 28 | | | 115-199 |
| 0247 | 20 | GA | | | 5-0 | 38-13-11 | C04134 | =L | D | | D41302J | 23 | | | 001-099 |
| 0247 | 20 | GA | | | 4-11 | 38-13-11 | C04134 | =L | D | | D41302J | 23 | | | 115-199 |
| 0248 | 20 | GA | | | 5-0 | 38-13-11 | C04135 | =L | D | | D41302J | 21 | | | 001-099 |
| 0248 | 18 | GA | | | 5-0 | 38-13-11 | C04135 | =L | D | | D41302J | 21 | | | 115-199 |
| 0250 | 24 | GK | | | 6-0 | 24-28-11 | D41748J | 13 | | | D41487J | 33 | | | 001-099 |
| 0250 | 24 | GK | | | 5-5 | 24-28-11 | D41748J | 13 | | | D41487J | 33 | | | 115-199 |
| 0251 | 24 | GK | | | 5-0 | 24-27-21 | D41748J | 4 | | | D41122J | 5 | | | 001-099 |
| 0251 | 24 | GK | | | 4-4 | 24-27-21 | D41748J | 4 | | | D41122J | 5 | | | 115-199 |
| 0252 | 24 | GK | | | 5-0 | 24-27-21 | D41748J | 3 | | | D41122J | 6 | | | 001-099 |
| 0252 | 24 | GK | | | 4-4 | 24-27-21 | D41748J | 3 | | | D41122J | 6 | | | 115-199 |
| 0253 | 22 | GA | | | 3-0 | 24-32-41 | D41122J | 4 | | | D41082J | 2 | | | 001-099 |
| 0253 | 22 | GA | | | 2-5 | 24-32-41 | D41122J | 4 | | | D41082J | 2 | | | 115-199 |
| 0254 | 20 | GA | | | 5-0 | 30-71-21 | C04262 | =L | D | | D40184J | 2 | | | 001-099 |
| 0254 | 24 | GK | | | 5-1 | 30-71-21 | C04262 | =L | D | | D40184J | 2 | | | 115-199 |
| 0255 | 12 | HA | | | 1-6 | 24-51-52 | C04262 | =B | D | | C00630 | =B | D | * | 001-008, 115-199 |
| 0301 | 12 | HA | | | 4-0 | 25-31-23 | C03024 | A1 | D | | TB5070 | 7 | E | | 115-199 |
| 0302 | 12 | HA | | | 4-0 | 25-31-23 | C03024 | B1 | D | | TB5070 | 8 | E | | 115-199 |
| 0303 | 12 | HA | | | 4-0 | 25-31-23 | C03024 | C1 | D | | TB5070 | 9 | E | | 115-199 |
| 0304 | 10 | HA | | | 3-9 | 25-31-11 | C03013 | A1 | D | | TB5070 | 10 | E | | 115-199 |
| 0305 | 10 | HA | | | 3-8 | 25-31-11 | C03013 | B1 | D | | TB5070 | 11 | E | | 115-199 |
| 0306 | 10 | HA | | | 3-8 | 25-31-11 | C03013 | C1 | D | | TB5070 | 12 | E | | 115-199 |
| 0307 | 22 | GA | | | 7-0 | 38-32-21 | C04169 | =L | D | * | D40496J | 8 | | | 001-099 |
| 0307 | 20 | GA | | | 6-2 | 38-32-21 | C04169 | =L | D | * | D40496J | 27 | | | 115-199 |
| 0308 | 22 | GA | | | 7-0 | 38-32-21 | C04169 | =L | D | * | D41302J | 16 | | | 001-099 |
| 0308 | 20 | GA | | | 6-3 | 38-32-21 | C04169 | =L | D | * | D41302J | 16 | | | 115-199 |
| 0315 | 10 | HA | | | 4-1 | 25-31-31 | C03046 | A2 | D | | TB5070 | 10 | E | | 001-099 |
| 0316 | 10 | HA | | | 4-2 | 25-31-31 | C03046 | B2 | D | | TB5070 | 11 | E | | 001-099 |
| 0317 | 10 | HA | | | 4-2 | 25-31-31 | C03046 | C2 | D | | TB5070 | 12 | E | | 001-099 |
| 0318 | 08 | HA | | | 3-5 | 24-51-24 | K10298 | A2 | E | | C03023 | A1 | D | * | 001-099 |
| 0319 | 08 | HA | | | 3-4 | 24-51-24 | K10298 | B2 | E | | C03023 | B1 | D | * | 001-099 |
| 0320 | 08 | HA | | | 3-5 | 24-51-24 | K10298 | C2 | E | | C03023 | C1 | D | * | 001-099 |
| 2001B | 12 | HB | AA | | 4-1 | 30-41-12 | C00392 | C2 | D | | D41122J | 16 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 66

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1272 | 286N1272 | | | P37 MODULE WIRING, CB PANEL (continued) | | | | | | | | | | | |
| 2001B | 12 | HB | AA | | 6-4 | 30-41-12 | C00392 | | C2 | D | D40920J | 1 | | | 115-199 |
| 2001R | 12 | HB | AA | | 0-0 | 30-41-12 | C00392 | | B2 | D | D41122J | 18 | | | 001-099 |
| 2001R | 12 | HB | AA | | 0-0 | 30-41-12 | C00392 | | B2 | D | D40920J | 2 | | | 115-199 |
| ZZAX | 02 | ZB | | | 0-0 | 24-51-52 | C01218 | | =B | D | C01219 | =B | D | | ALL |
| ZZXD | 02 | ZA | | | 0-0 | 24-51-52 | C00333 | | A2 | D | C03029 | A2 | D | | 115-199 |
| ZZXE | 02 | ZA | | | 0-0 | 24-51-52 | C00333 | | B2 | D | C03029 | B2 | D | | 115-199 |
| ZZXF | 02 | ZA | | | 0-0 | 24-51-52 | C00333 | | C2 | D | C03029 | C2 | D | | 115-199 |
| ZZXG | 02 | ZA | | | 0-0 | 24-51-52 | C00301 | | A2 | D | C00302 | A2 | D | | 115-199 |
| ZZXH | 02 | ZA | | | 0-0 | 24-51-52 | C00301 | | B2 | D | C00302 | B2 | D | | 115-199 |
| ZZXI | 02 | ZA | | | 0-0 | 24-51-52 | C00301 | | C2 | D | C00302 | C2 | D | | 115-199 |
| ZZXJ | 02 | ZA | | | 0-6 | 24-51-24 | C04075 | | =B | D | C04076 | =B | D | | 001-099 |
| ZZXJ | 02 | ZA | | | 0-0 | 24-51-24 | C04075 | | =B | D | C04076 | =B | D | | 115-199 |
| ZZXL | 02 | ZA | | | 0-5 | 24-51-52 | C01150 | | =B | D | C00871 | =B | D | | 001-099 |
| ZZXL | 02 | ZA | | | 0-0 | 24-51-52 | C01150 | | =B | D | C00871 | =B | D | | 115-199 |
| ZZXO | 02 | ZA | | | 0-6 | 24-51-52 | C01142 | | =B | D | C01149 | =B | D | | 001-099 |
| ZZXO | 02 | ZA | | | 0-0 | 24-51-52 | C01142 | | =B | D | C01149 | =B | D | | 115-199 |
| ZZXP | 02 | ZA | | | 0-6 | 24-51-52 | C01149 | | =B | D | C04247 | =B | D | | 001-099 |
| ZZXP | 02 | ZA | | | 0-0 | 24-51-52 | C01149 | | =B | D | C04247 | =B | D | | 115-199 |
| ZZXR | 02 | ZA | | | 0-6 | 24-51-24 | C00699 | | =B | D | C04028 | =B | D | | 001-099 |
| ZZXR | 02 | ZA | | | 0-0 | 24-51-24 | C00699 | | =B | D | C04028 | =B | D | | 115-199 |
| ZZXS | 02 | ZA | | | 0-0 | 24-51-52 | C01142 | | =B | D | C04285 | =B | D | | 115-199 |
| ZZYA | 02 | ZA | | | 0-0 | 24-51-24 | C00700 | | =B | D | C04135 | =B | D | | ALL |
| ZZYB | 02 | ZA | | | 0-0 | 24-51-21 | C01124 | | =B | D | C01126 | =B | D | | ALL |
| ZZYC | 02 | ZA | | | 0-0 | 24-51-52 | C04042 | | =B | D | C00871 | =B | D | | ALL |
| ZZYD | 02 | ZA | | | 0-0 | 24-51-52 | C01232 | | =B | D | C01255 | =B | D | | ALL |
| ZZYE | 02 | ZA | | | 0-0 | 24-51-52 | C00333 | | A2 | D | C00301 | A2 | D | | 001-099 |
| ZZYE | 02 | ZA | | | 0-0 | 24-51-52 | C03029 | | A2 | D | C00301 | A2 | D | | 115-199 |
| ZZYF | 02 | ZA | | | 0-0 | 24-51-52 | C00333 | | B2 | D | C00301 | B2 | D | | 001-099 |
| ZZYF | 02 | ZA | | | 0-0 | 24-51-52 | C03029 | | B2 | D | C00301 | B2 | D | | 115-199 |
| ZZYG | 02 | ZA | | | 0-0 | 24-51-52 | C00333 | | C2 | D | C00301 | C2 | D | | 001-099 |
| ZZYG | 02 | ZA | | | 0-0 | 24-51-52 | C03029 | | C2 | D | C00301 | C2 | D | | 115-199 |
| ZZYH | 02 | ZA | | | 0-0 | 24-51-52 | C04262 | | =B | D | C04169 | =B | D | | 001-099 |
| ZZYH | 02 | ZA | | | 0-0 | 24-51-24 | C03013 | | A2 | D | C03024 | A2 | D | | 115-199 |
| ZZYJ | 02 | ZA | | | 0-0 | 24-51-24 | C03013 | | B2 | D | C03024 | B2 | D | | 115-199 |
| ZZYK | 02 | ZA | | | 0-0 | 24-51-24 | C03013 | | C2 | D | C03024 | C2 | D | | 115-199 |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) | | | | | | | | | | | |
| 0002 | 24 | GK | | | 3-11 | 21-25-11 | D00319A | | E07 | | D40584J | 22 | | *C | 001-099 |
| 0002 | 24 | GK | | | 4-0 | 21-25-11 | D00319A | | E07 | | D40584J | 22 | | *C | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 67

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0003 | 24 | | GK | | 2-10 | 21-25-11 | D00319A | | D06 | | D41058J | 7 | | *E | ALL |
| 0005 | 24 | | GK | | 3-11 | 21-31-11 | D00319E | | F14 | | D40584J | 5 | | *C | ALL |
| 0006 | 24 | | GK | | 3-11 | 21-31-21 | D00319E | | F13 | | D40584J | 3 | | *C | ALL |
| 0008 | 24 | | GK | | 4-0 | 21-43-11 | D00319D | | A05 | | D40584J | 32 | | *C | ALL |
| 0009 | 24 | | GK | | 3-11 | 21-44-11 | D00319A | | J15 | | D41867J | 17 | | *Y | 001-099 |
| 0009 | 24 | | GK | | 4-0 | 21-44-11 | D00319A | | J15 | | D41867J | 17 | | *Y | 115-199 |
| 0011 | 24 | | GK | | 3-10 | 21-58-12 | D00319B | | G08 | | D40584J | 48 | | *C | 001-099 |
| 0011 | 24 | | GK | | 3-11 | 21-58-12 | D00319B | | G08 | | D40584J | 48 | | *C | 115-199 |
| 0013 | 24 | | GK | | 4-0 | 21-58-11 | D00319D | | A04 | | D40584J | 49 | | *C | ALL |
| 0015 | 24 | | GK | | 4-0 | 21-58-11 | D00319D | | A03 | | D40584J | 50 | | *C | ALL |
| 0017 | 24 | | GK | | 2-6 | 49-61-11 | D00319F | | B06 | | D41660J | 7 | | *K | 001-099 |
| 0017 | 24 | | GK | | 2-7 | 49-61-11 | D00319F | | B06 | | D41660J | 7 | | *K | 115-199 |
| 0023 | 24 | | GK | | 2-5 | 52-71-11 | D00319B | | A06 | | D41628J | 5 | | *J | 001-099 |
| 0023 | 24 | | GK | | 2-7 | 52-71-11 | D00319B | | A06 | | D41628J | 5 | | *J | 115-199 |
| 0025 | 24 | | GK | | 2-5 | 52-71-11 | D00319B | | B07 | | D41628J | 6 | | *J | 001-099 |
| 0025 | 24 | | GK | | 2-7 | 52-71-11 | D00319B | | B07 | | D41628J | 6 | | *J | 115-199 |
| 0027 | 24 | | GK | | 2-5 | 52-71-11 | D00319B | | E12 | | D41628J | 7 | | *J | 001-099 |
| 0027 | 24 | | GK | | 2-7 | 52-71-11 | D00319B | | E12 | | D41628J | 7 | | *J | 115-199 |
| 0029 | 24 | | GK | | 2-5 | 52-71-11 | D00319B | | B12 | | D41628J | 8 | | *J | 001-099 |
| 0029 | 24 | | GK | | 2-7 | 52-71-11 | D00319B | | B12 | | D41628J | 8 | | *J | 115-199 |
| 0030 | 24 | | GK | | 2-4 | 52-71-11 | D41628J | | 9 | | TB0207Y | A080 | BJ | | 001-099 |
| 0030 | 24 | | GK | | 2-7 | 52-71-11 | D41628J | | 9 | | TB0207Y | A080 | BJ | | 115-199 |
| 0031 | 24 | | GK | | 2-9 | 52-71-11 | D00319B | | A11 | | TB0207Y | A080 | BJ | | 001-099 |
| 0031 | 24 | | GK | | 2-11 | 52-71-11 | D00319B | | A11 | | TB0207Y | A080 | BJ | | 115-199 |
| 0032 | 24 | | GK | | 2-4 | 52-71-11 | D41628J | | 10 | | TB0207Y | C080 | BJ | | 001-099 |
| 0032 | 24 | | GK | | 2-7 | 52-71-11 | D41628J | | 10 | | TB0207Y | C080 | BJ | | 115-199 |
| 0033 | 24 | | GK | | 2-9 | 52-71-11 | D00319B | | A10 | | TB0207Y | C080 | BJ | | 001-099 |
| 0033 | 24 | | GK | | 2-11 | 52-71-11 | D00319B | | A10 | | TB0207Y | C080 | BJ | | 115-199 |
| 0034 | 24 | | GK | | 3-3 | 52-71-21 | D41451J | | 44 | | TB0207Y | A057 | BJ | | 001-099 |
| 0034 | 24 | | GK | | 3-4 | 52-71-21 | D41451J | | 44 | | TB0207Y | A057 | BJ | | 115-199 |
| 0035 | 24 | | GK | | 2-9 | 21-25-11 | D00321A | | E07 | | D40584J | 22 | | *C | ALL |
| 0036 | 24 | | GK | | 4-3 | 21-25-11 | D00321A | | D06 | | D41058J | 7 | | *E | ALL |
| 0037 | 24 | | GK | | 2-9 | 21-31-11 | D00321E | | F14 | | D40584J | 5 | | *C | 001-099 |
| 0037 | 24 | | GK | | 2-10 | 21-31-11 | D00321E | | F14 | | D40584J | 5 | | *C | 115-199 |
| 0039 | 24 | | GK | | 2-9 | 21-31-21 | D00321E | | F13 | | D40584J | 3 | | *C | 001-099 |
| 0039 | 24 | | GK | | 2-10 | 21-31-21 | D00321E | | F13 | | D40584J | 3 | | *C | 115-199 |
| 0041 | 24 | | GK | | 5-4 | 21-44-11 | D00321A | | J15 | | D41867J | 17 | | *Y | 001-099 |
| 0041 | 24 | | GK | | 5-5 | 21-44-11 | D00321A | | J15 | | D41867J | 17 | | *Y | 115-199 |
| 0042 | 24 | | GK | | 2-8 | 21-58-12 | D00321B | | G08 | | D40584J | 48 | | *C | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 68

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0043 | 24 | | GK | | 2-10 | 21-58-11 | D00321D | | A04 | | D40584J | 49 | | *C | 001-099 |
| 0043 | 24 | | GK | | 2-11 | 21-58-11 | D00321D | | A04 | | D40584J | 49 | | *C | 115-199 |
| 0044 | 24 | | GK | | 2-10 | 21-58-11 | D00321D | | A03 | | D40584J | 50 | | *C | 001-099 |
| 0044 | 24 | | GK | | 2-11 | 21-58-11 | D00321D | | A03 | | D40584J | 50 | | *C | 115-199 |
| 0046 | 24 | | GK | | 2-10 | 21-43-11 | D00321D | | A05 | | D40584J | 32 | | *C | 001-099 |
| 0046 | 24 | | GK | | 2-11 | 21-43-11 | D00321D | | A05 | | D40584J | 32 | | *C | 115-199 |
| 0049 | 24 | | GK | | 3-6 | 52-71-11 | D00321B | | A06 | | D41628J | 5 | | *J | ALL |
| 0050 | 24 | | GK | | 3-6 | 52-71-11 | D00321B | | B07 | | D41628J | 6 | | *J | ALL |
| 0051 | 24 | | GK | | 3-6 | 52-71-11 | D00321B | | E12 | | D41628J | 7 | | *J | ALL |
| 0052 | 24 | | GK | | 3-6 | 52-71-11 | D00321B | | B12 | | D41628J | 8 | | *J | ALL |
| 0053 | 24 | | GK | | 3-0 | 52-71-11 | D00321B | | A11 | | TB0207Y | A080 | BJ | | 001, 003-099 |
| 0053 | 24 | | GK | | 3-1 | 52-71-11 | D00321B | | A11 | | TB0207Y | A080 | BJ | | 002 |
| 0053 | 24 | | GK | | 3-2 | 52-71-11 | D00321B | | A11 | | TB0207Y | A080 | BJ | | 115-199 |
| 0054 | 24 | | GK | | 3-0 | 52-71-11 | D00321B | | A10 | | TB0207Y | C080 | BJ | | 001, 003-099 |
| 0054 | 24 | | GK | | 3-1 | 52-71-11 | D00321B | | A10 | | TB0207Y | C080 | BJ | | 002 |
| 0054 | 24 | | GK | | 3-2 | 52-71-11 | D00321B | | A10 | | TB0207Y | C080 | BJ | | 115-199 |
| 0055 | 24 | | GK | | 3-8 | 52-71-21 | D00321A | | D14 | | TB0207Y | A057 | BJ | | 001-099 |
| 0055 | 24 | | GK | | 3-9 | 52-71-21 | D00321A | | D14 | | TB0207Y | A057 | BJ | | 115-199 |
| 0056 | 24 | | GK | | 3-7 | 52-71-21 | D00321B | | A05 | | TB0207Y | C057 | BJ | | 001-099 |
| 0056 | 24 | | GK | | 3-8 | 52-71-21 | D00321B | | A05 | | TB0207Y | C057 | BJ | | 115-199 |
| 0057 | 24 | | GK | | 3-0 | 52-71-21 | D00321B | | D05 | | D41451J | 43 | | *H | ALL |
| 0058 | 24 | | GK | | 3-1 | 52-71-21 | D00321A | | D13 | | D41451J | 39 | | *H | ALL |
| 0059 | 24 | | GK | | 3-1 | 52-71-21 | D00321A | | F15 | | D41451J | 45 | | *H | ALL |
| 0060 | 24 | | GK | | 3-0 | 52-71-21 | D00321B | | A07 | | D41451J | 46 | | *H | 001-099 |
| 0060 | 24 | | GK | | 3-0 | 52-71-21 | D00321B | | C05 | | D41451J | 46 | | *H | 115-199 |
| 0061 | 24 | | GK | | 2-5 | 52-71-21 | D00319A | | D14 | | TB0207Y | A057 | BJ | | 001-099 |
| 0061 | 24 | | GK | | 2-7 | 52-71-21 | D00319A | | D14 | | TB0207Y | A057 | BJ | | 115-199 |
| 0062 | 24 | | GK | | 2-4 | 52-71-21 | D00319B | | A05 | | TB0207Y | C057 | BJ | | 001-099 |
| 0062 | 24 | | GK | | 2-6 | 52-71-21 | D00319B | | A05 | | TB0207Y | C057 | BJ | | 115-199 |
| 0063 | 24 | | GK | | 3-7 | 52-71-21 | D00319B | | D05 | | D41451J | 43 | | *H | ALL |
| 0064 | 24 | | GK | | 3-8 | 52-71-21 | D00319A | | D13 | | D41451J | 39 | | *H | 001-099 |
| 0064 | 24 | | GK | | 3-9 | 52-71-21 | D00319A | | D13 | | D41451J | 39 | | *H | 115-199 |
| 0065 | 24 | | GK | | 3-8 | 52-71-21 | D00319A | | F15 | | D41451J | 45 | | *H | 001-099 |
| 0065 | 24 | | GK | | 3-9 | 52-71-21 | D00319A | | F15 | | D41451J | 45 | | *H | 115-199 |
| 0066 | 24 | | GK | | 3-7 | 52-71-21 | D00319B | | A07 | | D41451J | 46 | | *H | 001-099 |
| 0066 | 24 | | GK | | 3-7 | 52-71-21 | D00319B | | C05 | | D41451J | 46 | | *H | 115-199 |
| 0067 | 24 | | GK | | 3-3 | 52-71-21 | D41451J | | 42 | | TB0207Y | C057 | BJ | | 001-099 |
| 0067 | 24 | | GK | | 3-4 | 52-71-21 | D41451J | | 42 | | TB0207Y | C057 | BJ | | 115-199 |
| 0073 | 24 | | GK | | 3-1 | 73-33-11 | D00321A | | K07 | | D41774J | 1 | | *U | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 69

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0073 | 24 | | GK | | 3-0 | 73-33-11 | D00321A | K07 | | | D41774J | 1 | | *U | 115-199 |
| 0074 | 24 | | GK | | 3-8 | 73-33-11 | D00319A | K07 | | | D41774J | 1 | | *U | 001-099 |
| 0074 | 24 | | GK | | 4-3 | 73-33-11 | D00319A | K07 | | | D41774J | 1 | | *U | 115-199 |
| 0076 | 24 | | GK | | 2-8 | 73-33-11 | D00319A | J11 | | | D41764J | 1 | | *S | 001-099 |
| 0076 | 24 | | GK | | 3-7 | 73-33-11 | D00319A | J11 | | | D41764J | 1 | | *S | 115-199 |
| 0077 | 24 | | GK | | 3-8 | 73-33-11 | D00321A | J11 | | | D41764J | 1 | | *S | 001-099 |
| 0077 | 24 | | GK | | 4-11 | 73-33-11 | D00321A | J11 | | | D41764J | 1 | | *S | 115-199 |
| 0080 | 24 | | GK | | 3-1 | 77-12-11 | D00321A | E08 | | | D42093J | 1 | | | 001-099 |
| 0080 | 24 | | GK | | 3-2 | 77-12-11 | D00321A | E08 | | | D42093J | 1 | | | 115-199 |
| 0081 | 24 | | GK | | 2-8 | 77-12-11 | D00319A | E08 | | | D42073J | 24 | | | 001-099 |
| 0081 | 24 | | GK | | 2-9 | 77-12-11 | D00319A | E08 | | | D42073J | 10 | | | 115-199 |
| 0086 | 24 | | GK | | 3-8 | 26-13-11 | D00321A | H07 | | | D41764J | 16 | | *S | 001-099 |
| 0086 | 24 | | GK | | 4-11 | 26-13-11 | D00321A | H07 | | | D41764J | 16 | | *S | 115-199 |
| 0087 | 24 | | GK | | 3-8 | 31-31-01 | D00319A | J14 | | | D41451J | 52 | | *H | 001-099 |
| 0087 | 24 | | GK | | 3-9 | 31-31-13 | D00319A | J14 | | | D41451J | 52 | | *H | 115-199 |
| 0089 | 24 | | GK | | 3-1 | 31-31-01 | D00321A | J14 | | | D41451J | 52 | | *H | 001-099 |
| 0089 | 24 | | GK | | 3-1 | 31-31-13 | D00321A | J14 | | | D41451J | 52 | | *H | 115-199 |
| 0090 | 24 | | GK | | 2-8 | 26-13-11 | D00319A | H07 | | | D41764J | 16 | | *S | 001-099 |
| 0090 | 24 | | GK | | 3-7 | 26-13-11 | D00319A | H07 | | | D41764J | 16 | | *S | 115-199 |
| 0091 | 24 | | GK | | 2-10 | 26-13-11 | D00321B | G02 | | | D41738J | 8 | | *R | 001-099 |
| 0091 | 24 | | GK | | 2-11 | 26-13-11 | D00321B | G02 | | | D41738J | 8 | | *R | 115-199 |
| 0092 | 24 | | GK | | 4-1 | 26-13-11 | D00319B | G02 | | | D41738J | 8 | | *R | 001-099 |
| 0092 | 24 | | GK | | 4-2 | 26-13-11 | D00319B | G02 | | | D41738J | 8 | | *R | 115-199 |
| 0094 | 24 | | GK | | 3-0 | 26-13-21 | D00321D | F05 | | | D41774J | 15 | | *U | 001-099 |
| 0094 | 24 | | GK | | 3-1 | 26-13-21 | D00321D | F05 | | | D41774J | 15 | | *U | 115-199 |
| 0095 | 24 | | GK | | 3-9 | 26-13-21 | D00319D | F05 | | | D41774J | 15 | | *U | 001-099 |
| 0095 | 24 | | GK | | 4-3 | 26-13-21 | D00319D | F05 | | | D41774J | 15 | | *U | 115-199 |
| 0100 | 24 | | GK | | 3-5 | 26-13-21 | D00321E | G05 | | | D41776J | 3 | | *V | ALL |
| 0101 | 24 | | GK | | 3-2 | 26-13-21 | D00319E | G05 | | | D41776J | 3 | | *V | 001-099 |
| 0101 | 24 | | GK | | 3-1 | 26-13-21 | D00319E | G05 | | | D41776J | 3 | | *V | 115-199 |
| 0104 | 24 | | GK | | 2-2 | 79-32-11 | D40704J | 2 | | | TB0207Y | C083 | BJ | | 001-099 |
| 0104 | 22 | | GA | | 3-9 | 79-32-11 | D40704J | 2 | | | TB0207Y | C001 | BJ | | 115-199 |
| 0105 | 24 | | GK | | 3-7 | 79-32-11 | D40684J | 3 | | | TB0207Y | C084 | BJ | | 001-099 |
| 0105 | 24 | | GK | | 2-5 | 79-32-11 | D40684J | 3 | | | TB0207Y | C002 | BJ | | 115-199 |
| 0106 | 22 | | GA | | 4-7 | 79-33-11 | D41774J | 3 | | | TB0207Y | A011 | BJ | | 001, 003-099 |
| 0106 | 22 | | GA | | 4-8 | 79-33-11 | D41774J | 3 | | | TB0207Y | A011 | BJ | | 002 |
| 0106 | 22 | | GA | | 5-0 | 79-33-11 | D41774J | 3 | | | TB0207Y | A011 | BJ | | 115-199 |
| 0107 | 24 | | GK | | 4-10 | 79-33-11 | D00321D | K10 | | | TB0207Y | A011 | BJ | | 001, 003-099 |
| 0107 | 24 | | GK | | 4-11 | 79-33-11 | D00321D | K10 | | | TB0207Y | A011 | BJ | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 70

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0107 | 24 | | GK | | 4-9 | 79-33-11 | D00321D | | K10 | | TB0207Y | A011 | BJ | | 115-199 |
| 0108 | 24 | | GK | | 3-6 | 79-33-11 | D00319D | | K10 | | TB0207Y | A011 | BJ | | 001, 003-099, 115-199 |
| 0108 | 24 | | GK | | 3-7 | 79-33-11 | D00319D | | K10 | | TB0207Y | A011 | BJ | | 002 |
| 0109 | 22 | | GA | | 3-6 | 79-33-11 | D41764J | | 9 | | TB0207Y | C011 | BJ | | 001, 003-099 |
| 0109 | 22 | | GA | | 3-7 | 79-33-11 | D41764J | | 9 | | TB0207Y | C011 | BJ | | 002 |
| 0109 | 22 | | GA | | 2-8 | 79-33-11 | D41764J | | 9 | | TB0207Y | C011 | BJ | | 115-199 |
| 0110 | 24 | | GK | | 4-11 | 79-33-11 | D00321A | | H03 | | TB0207Y | C011 | BJ | | 001, 003-099 |
| 0110 | 24 | | GK | | 5-0 | 79-33-11 | D00321A | | H03 | | TB0207Y | C011 | BJ | | 002 |
| 0110 | 24 | | GK | | 4-10 | 79-33-11 | D00321A | | H03 | | TB0207Y | C011 | BJ | | 115-199 |
| 0111 | 24 | | GK | | 3-7 | 79-33-11 | D00319A | | H03 | | TB0207Y | C011 | BJ | | 001-099 |
| 0111 | 24 | | GK | | 3-6 | 79-33-11 | D00319A | | H03 | | TB0207Y | C011 | BJ | | 115-199 |
| 0113 | 24 | | GK | | 3-0 | 79-35-11 | D00321D | | K03 | | D41774J | 10 | | *U | 001-099 |
| 0113 | 24 | | GK | | 3-1 | 79-35-11 | D00321D | | K03 | | D41774J | 10 | | *U | 115-199 |
| 0114 | 24 | | GK | | 3-9 | 79-35-11 | D00319D | | K03 | | D41774J | 10 | | *U | 001-099 |
| 0114 | 24 | | GK | | 4-3 | 79-35-11 | D00319D | | K03 | | D41774J | 10 | | *U | 115-199 |
| 0116 | 24 | | GK | | 2-8 | 79-35-11 | D00319A | | H04 | | D41764J | 14 | | *S | 001-099 |
| 0116 | 24 | | GK | | 3-7 | 79-35-11 | D00319A | | H04 | | D41764J | 14 | | *S | 115-199 |
| 0117 | 24 | | GK | | 3-8 | 79-35-11 | D00321A | | H04 | | D41764J | 14 | | *S | 001-099 |
| 0117 | 24 | | GK | | 4-11 | 79-35-11 | D00321A | | H04 | | D41764J | 14 | | *S | 115-199 |
| 0118 | 24 | | GK | | 3-10 | 36-11-31 | D00319B | | B13 | | D40584J | 41 | | *C | 001-099 |
| 0118 | 24 | | GK | | 3-11 | 36-11-31 | D00319B | | B13 | | D40584J | 41 | | *C | 115-199 |
| 0119 | 24 | | GK | | 2-8 | 36-11-31 | D00321B | | B13 | | D40584J | 41 | | *C | ALL |
| 0120 | 22 | | GA | | 2-3 | 49-61-11 | D41660J | | 8 | | TB0207Y | A044 | BJ | | 001, 003-099, 115-199 |
| 0120 | 22 | | GA | | 2-4 | 49-61-11 | D41660J | | 8 | | TB0207Y | A044 | BJ | | 002 |
| 0121 | 22 | | GA | | 4-4 | 49-61-11 | D41738J | | 18 | | D41660J | 1 | | | 001-099 |
| 0121 | 22 | | GA | | 4-5 | 49-61-11 | D41738J | | 18 | | D41660J | 1 | | | 115-199 |
| 0123 | 22 | | GA | | 3-2 | 49-61-11 | D40602J | | 1 | | D41660J | 3 | | | 001-099 |
| 0123 | 22 | | GA | | 3-0 | 49-61-11 | D40602J | | 1 | | D41660J | 3 | | | 115-199 |
| 0124 | 22 | | GA | | 3-2 | 49-61-11 | D40602J | | 2 | | D41660J | 4 | | | 001-099 |
| 0124 | 22 | | GA | | 3-0 | 49-61-11 | D40602J | | 2 | | D41660J | 4 | | | 115-199 |
| 0125 | 22 | | GA | | 3-2 | 49-61-11 | D40602J | | 3 | | D41660J | 5 | | | 001-099 |
| 0125 | 22 | | GA | | 3-0 | 49-61-11 | D40602J | | 3 | | D41660J | 5 | | | 115-199 |
| 0126 | 22 | | GA | | 3-2 | 49-61-11 | D40602J | | 4 | | D41660J | 6 | | | 001-099 |
| 0126 | 22 | | GA | | 3-0 | 49-61-11 | D40602J | | 4 | | D41660J | 6 | | | 115-199 |
| 0127 | 22 | | GA | | 3-2 | 49-61-11 | D40602J | | 5 | | D41660J | 29 | | | 001-099 |
| 0127 | 22 | | GA | | 3-0 | 49-61-11 | D40602J | | 5 | | D41660J | 29 | | | 115-199 |
| 0129 | 24 | | GK | | 3-11 | 49-61-11 | D00321F | | B06 | | D41660J | 7 | | *K | ALL |
| 0133 | 24 | | GK | | 3-5 | 24-11-11 | D40584J | | 24 | | TB0207B | C061 | 2 | | 001, 003-099 |
| 0133 | 24 | | GK | | 3-6 | 24-11-11 | D40584J | | 24 | | TB0207B | C061 | 2 | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 71

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0133 | 24 | | GK | | 3-7 | 24-11-11 | D40584J | | 24 | | TB0207B | C061 | 2 | | 115-199 |
| 0135 | 24 | | GK | | 3-4 | 24-11-11 | D00321E | | E07 | | TB0207B | C061 | 2 | *2 | 001, 003-099 |
| 0135 | 24 | | GK | | 3-5 | 24-11-11 | D00321E | | E07 | | TB0207B | C061 | 2 | *2 | 002, 115-199 |
| 0136 | 24 | | GK | | 2-6 | 24-11-11 | D00319E | | E07 | | TB0207B | C061 | 2 | *2 | ALL |
| 0140 | 24 | | GK | | 2-8 | 24-11-11 | D00321B | | B05 | | D40584J | 26 | | *C | ALL |
| 0141 | 24 | | GK | | 2-10 | 24-11-11 | D00321D | | A10 | | D40584J | 25 | | *C | 001-099 |
| 0141 | 24 | | GK | | 2-11 | 24-11-11 | D00321D | | A10 | | D40584J | 25 | | *C | 115-199 |
| 0142 | 24 | | GK | | 3-10 | 24-11-11 | D00319B | | B05 | | D40584J | 26 | | *C | 001-099 |
| 0142 | 24 | | GK | | 3-11 | 24-11-11 | D00319B | | B05 | | D40584J | 26 | | *C | 115-199 |
| 0143 | 24 | | GK | | 4-0 | 24-11-11 | D00319D | | A10 | | D40584J | 25 | | *C | ALL |
| 0145 | 24 | | GK | | 2-8 | 24-11-21 | D41058J | | 20 | | TB0207B | C062 | 2 | | 001, 003-099 |
| 0145 | 24 | | GK | | 2-9 | 24-11-21 | D41058J | | 20 | | TB0207B | C062 | 2 | | 002 |
| 0145 | 24 | | GK | | 2-10 | 24-11-21 | D41058J | | 20 | | TB0207B | C062 | 2 | | 115-199 |
| 0148 | 24 | | GK | | 2-6 | 24-11-21 | D00319E | | E08 | | TB0207B | C062 | 2 | *4 | ALL |
| 0149 | 24 | | GK | | 2-9 | 24-11-21 | D00319D | | A01 | | D41058J | 18 | | *E | 001-099 |
| 0149 | 24 | | GK | | 2-10 | 24-11-21 | D00319D | | A01 | | D41058J | 18 | | *E | 115-199 |
| 0150 | 24 | | GK | | 3-4 | 24-11-21 | D00321E | | E08 | | TB0207B | C062 | 2 | *4 | 001, 003-099 |
| 0150 | 24 | | GK | | 3-5 | 24-11-21 | D00321E | | E08 | | TB0207B | C062 | 2 | *4 | 002, 115-199 |
| 0151 | 24 | | GK | | 4-2 | 24-11-21 | D00321D | | A01 | | D41058J | 18 | | *E | ALL |
| 0154 | 24 | | GK | | 3-2 | 34-53-11 | D00319E | | A13 | | TB0207Y | C089 | BJ | | 001, 003-099 |
| 0154 | 24 | | GK | | 3-3 | 34-53-11 | D00319E | | A13 | | TB0207Y | C089 | BJ | | 002 |
| 0154 | 24 | | GK | | 2-11 | 34-53-11 | D00319E | | A13 | | TB0207A | A081 | 2 | | 115-199 |
| 0155 | 24 | | GK | | 2-7 | 34-53-11 | D00321E | | A13 | | TB0207Y | C089 | BJ | | 001-099 |
| 0155 | 24 | | GK | | 3-1 | 34-53-11 | D00321E | | A13 | | TB0207A | A082 | 2 | | 115-199 |
| 0157 | 24 | | GK | | 3-7 | 34-16-11 | D00319B | | E14 | | D41451J | 22 | | *H | ALL |
| 0158 | 24 | | GK | | 3-0 | 34-16-11 | D00321B | | E14 | | D41451J | 22 | | *H | ALL |
| 0160 | 24 | | GK | | 3-7 | 31-51-42 | D00319B | | G14 | | D41451J | 21 | | *H | ALL |
| 0161 | 24 | | GK | | 3-0 | 31-51-42 | D00321B | | G14 | | D41451J | 21 | | *H | ALL |
| 0163 | 24 | | GK | | 3-8 | 31-51-41 | D00319E | | D02 | | D41451J | 13 | | *H | 001-099 |
| 0163 | 24 | | GK | | 3-7 | 31-51-41 | D00319E | | D02 | | D41451J | 13 | | *H | 115-199 |
| 0164 | 24 | | GK | | 2-11 | 31-51-41 | D00321E | | D02 | | D41451J | 13 | | *H | ALL |
| 0166 | 24 | | GK | | 3-9 | 31-51-41 | D00319D | | A15 | | D41451J | 12 | | *H | 001-099 |
| 0166 | 24 | | GK | | 3-8 | 31-51-41 | D00319D | | A15 | | D41451J | 12 | | *H | 115-199 |
| 0167 | 24 | | GK | | 3-0 | 31-51-41 | D00321D | | A15 | | D41451J | 12 | | *H | ALL |
| 0169 | 24 | | GK | | 3-8 | 31-51-41 | D00319A | | G15 | | D41451J | 15 | | *H | 001-099 |
| 0169 | 24 | | GK | | 3-9 | 31-51-41 | D00319A | | G15 | | D41451J | 15 | | *H | 115-199 |
| 0170 | 24 | | GK | | 3-1 | 31-51-41 | D00321A | | G15 | | D41451J | 15 | | *H | ALL |
| 0172 | 24 | | GK | | 3-8 | 31-51-41 | D00319E | | A01 | | D41451J | 14 | | *H | 001-099 |
| 0172 | 24 | | GK | | 3-7 | 31-51-41 | D00319E | | A01 | | D41451J | 14 | | *H | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 72

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0173 | 24 | | GK | | 2-11 | 31-51-41 | D00321E | A01 | | | D41451J | 14 | | *H | ALL |
| 0178 | 24 | | GK | | 3-7 | 31-51-11 | D00319B | C08 | | | D41451J | 11 | | *H | ALL |
| 0179 | 24 | | GK | | 3-0 | 31-51-11 | D00321B | C08 | | | D41451J | 11 | | *H | ALL |
| 0183 | 24 | | GK | | 3-2 | 30-21-11 | D00319E | A05 | | | D41736J | 31 | | *Q | 001-099 |
| 0183 | 24 | | GK | | 3-1 | 30-21-11 | D00319E | A05 | | | D41736J | 31 | | *Q | 115-199 |
| 0184 | 24 | | GK | | 3-5 | 30-21-11 | D00321E | A05 | | | D41736J | 31 | | *Q | ALL |
| 0185 | 24 | | GK | | 3-9 | 30-21-11 | D00321F | G08 | | | TB0207Y | A048 | BJ | | ALL |
| 0186 | 24 | | GK | | 3-2 | 30-21-11 | D41736J | 1 | | | TB0207Y | A048 | BJ | | ALL |
| 0187 | 24 | | GK | | 2-4 | 30-21-11 | D00319F | G08 | | | TB0207Y | A048 | BJ | | 001-099 |
| 0187 | 24 | | GK | | 2-5 | 30-21-11 | D00319F | G08 | | | TB0207Y | A048 | BJ | | 115-199 |
| 0188 | 24 | | GK | | 2-6 | 30-21-11 | D41734J | 5 | | | TB0207Y | C060 | BJ | | 001-099 |
| 0188 | 24 | | GK | | 2-7 | 30-21-11 | D41734J | 1 | | | TB0207Y | C060 | BJ | | 115-199 |
| 0189 | 24 | | GK | | 3-4 | 30-21-11 | D00321F | G05 | | | TB0207Y | C060 | BJ | | 001-099 |
| 0189 | 24 | | GK | | 3-5 | 30-21-11 | D00321F | G05 | | | TB0207Y | C060 | BJ | | 115-199 |
| 0190 | 24 | | GK | | 2-3 | 30-21-11 | D00319F | G05 | | | TB0207Y | C060 | BJ | | 001-099 |
| 0190 | 24 | | GK | | 2-4 | 30-21-11 | D00319F | G05 | | | TB0207Y | C060 | BJ | | 115-199 |
| 0194 | 24 | | GK | | 2-11 | 30-21-11 | D00319E | C14 | | | D41734J | 20 | | *P | 001-099 |
| 0194 | 24 | | GK | | 2-10 | 30-21-11 | D00319E | C14 | | | D41734J | 7 | | *P | 115-199 |
| 0195 | 24 | | GK | | 3-2 | 30-21-11 | D00321E | C14 | | | D41734J | 20 | | *P | 001-099 |
| 0195 | 24 | | GK | | 3-2 | 30-21-11 | D00321E | C14 | | | D41734J | 7 | | *P | 115-199 |
| 0196 | 24 | | GK | | 3-8 | 31-31-01 | D00319E | C10 | | | D41451J | 5 | | *H | 001-099 |
| 0196 | 24 | | GK | | 3-7 | 31-31-13 | D00319E | C10 | | | D41451J | 5 | | *H | 115-199 |
| 0198 | 24 | | GK | | 2-11 | 31-31-01 | D00321E | C10 | | | D41451J | 5 | | *H | 001-099 |
| 0198 | 24 | | GK | | 2-11 | 31-31-13 | D00321E | C10 | | | D41451J | 5 | | *H | 115-199 |
| 0199 | 24 | | GK | | 3-9 | 30-31-11 | D00321E | C03 | | | D41698J | 21 | | *M | 001-099 |
| 0199 | 24 | | GK | | 3-8 | 30-31-11 | D00321E | C03 | | | D41698J | 21 | | *M | 115-199 |
| 0200 | 24 | | GK | | 3-7 | 30-31-11 | D00321F | B08 | | | D41698J | 19 | | *M | ALL |
| 0201 | 24 | | GK | | 2-8 | 30-31-11 | D00319F | B08 | | | D41698J | 19 | | *M | ALL |
| 0202 | 24 | | GK | | 3-11 | 30-31-11 | D00321A | D01 | | | D41698J | 22 | | *M | ALL |
| 0203 | 24 | | GK | | 3-9 | 30-31-11 | D00321E | K05 | | | D41698J | 20 | | *M | 001-099 |
| 0203 | 24 | | GK | | 3-8 | 30-31-11 | D00321E | K05 | | | D41698J | 20 | | *M | 115-199 |
| 0204 | 24 | | GK | | 2-10 | 30-31-11 | D00319E | K05 | | | D41698J | 20 | | *M | 001-099 |
| 0204 | 24 | | GK | | 2-9 | 30-31-11 | D00319E | K05 | | | D41698J | 20 | | *M | 115-199 |
| 0205 | 24 | | GK | | 3-3 | 30-31-12 | D00321E | K08 | | | D41720J | 6 | | *N | ALL |
| 0206 | 24 | | GK | | 3-3 | 30-31-12 | D00321E | A06 | | | D41720J | 9 | | *N | ALL |
| 0207 | 24 | | GK | | 3-0 | 30-31-12 | D00319E | A06 | | | D41720J | 9 | | *N | ALL |
| 0208 | 24 | | GK | | 3-0 | 30-31-12 | D00319E | K08 | | | D41720J | 6 | | *N | ALL |
| 0209 | 24 | | GK | | 3-5 | 30-31-12 | D00321D | B09 | | | D41720J | 8 | | *N | ALL |
| 0210 | 24 | | GK | | 3-1 | 30-31-12 | D00319D | B09 | | | D41720J | 8 | | *N | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 73

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0211 | 24 | | GK | | 2-5 | 30-33-11 | D41840J | | 1 | | TB0207Y | A047 | BJ | | ALL |
| 0212 | 24 | | GK | | 2-5 | 30-33-11 | D41317J | | 34 | | TB0207Y | A047 | BJ | | ALL |
| 0213 | 24 | | GK | | 3-11 | 30-33-11 | D00321E | | A04 | | TB0207Y | A047 | BJ | | 001-099 |
| 0213 | 24 | | GK | | 3-10 | 30-33-11 | D00321E | | A04 | | TB0207Y | A047 | BJ | | 115-199 |
| 0214 | 24 | | GK | | 2-6 | 30-33-11 | D00319E | | A04 | | TB0207Y | A047 | BJ | | ALL |
| 0216 | 24 | | GK | | 3-3 | 30-32-11 | D00321E | | A07 | | D41720J | 12 | | *N | ALL |
| 0217 | 24 | | GK | | 3-0 | 30-32-11 | D00319E | | A07 | | D41720J | 12 | | *N | ALL |
| 0219 | 24 | | GK | | 3-10 | 30-32-11 | D00321D | | B05 | | D41698J | 31 | | *M | 001-099 |
| 0219 | 24 | | GK | | 3-10 | 30-32-11 | D00321D | | B05 | | D41698J | 32 | | *M | 115-199 |
| 0220 | 24 | | GK | | 2-11 | 30-32-11 | D00319D | | B05 | | D41698J | 31 | | *M | 001-099 |
| 0220 | 24 | | GK | | 2-11 | 30-32-11 | D00319D | | B05 | | D41698J | 32 | | *M | 115-199 |
| 0222 | 24 | | GK | | 4-2 | 30-41-11 | D00321E | | C06 | | D41840J | 2 | | *W | ALL |
| 0223 | 24 | | GK | | 2-9 | 30-41-11 | D00319E | | C06 | | D41840J | 2 | | *W | 001-099 |
| 0223 | 24 | | GK | | 2-10 | 30-41-11 | D00319E | | C06 | | D41840J | 2 | | *W | 115-199 |
| 0225 | 24 | | GK | | 4-4 | 30-41-11 | D00321A | | D02 | | D41840J | 3 | | *W | ALL |
| 0226 | 24 | | GK | | 2-11 | 30-41-11 | D00319A | | D02 | | D41840J | 3 | | *W | 001-099 |
| 0226 | 24 | | GK | | 3-0 | 30-41-11 | D00319A | | D02 | | D41840J | 3 | | *W | 115-199 |
| 0228 | 24 | | GK | | 3-0 | 30-41-12 | D00321E | | C05 | | D41842J | 3 | | *1 | 001-099 |
| 0228 | 24 | | GK | | 3-1 | 30-41-12 | D00321E | | C05 | | D41842J | 3 | | *1 | 115-199 |
| 0229 | 24 | | GK | | 4-2 | 30-41-12 | D00319E | | C05 | | D41842J | 3 | | *1 | ALL |
| 0231 | 24 | | GK | | 3-0 | 30-41-12 | D00321E | | C04 | | D41842J | 4 | | *1 | 001-099 |
| 0231 | 24 | | GK | | 3-1 | 30-41-12 | D00321E | | C04 | | D41842J | 4 | | *1 | 115-199 |
| 0232 | 24 | | GK | | 4-2 | 30-41-12 | D00319E | | C04 | | D41842J | 4 | | *1 | ALL |
| 0233 | 22 | | GA | | 1-0 | 77-31-11 | D04240A | | A02 | | D04240A | D13 | | | ALL |
| 0234 | 22 | | GA | | 1-0 | 77-31-11 | D04240A | | A13 | | D04240A | C13 | | | ALL |
| 0235 | 22 | | GA | | 1-0 | 77-31-11 | D04240A | | A11 | | D04240A | C09 | | | ALL |
| 0236 | 22 | | GA | | 1-0 | 77-31-11 | D05602A | | A02 | | D05602A | D13 | | | ALL |
| 0237 | 22 | | GA | | 1-0 | 77-31-11 | D05602A | | A13 | | D05602A | C13 | | | ALL |
| 0238 | 22 | | GA | | 1-0 | 77-31-11 | D05602A | | A11 | | D05602A | C09 | | | ALL |
| 0244 | 24 | | GK | | 3-5 | 34-21-31 | D00319F | | C03 | | D41409J | 1 | | *U | 001-099 |
| 0244 | 24 | | GK | | 3-4 | 34-21-31 | D00319F | | C03 | | D41409J | 1 | | *1 | 115-199 |
| 0245 | 24 | | GK | | 2-8 | 34-21-31 | D00321F | | C03 | | D41409J | 1 | | *U | 001-099 |
| 0245 | 24 | | GK | | 2-8 | 34-21-31 | D00321F | | C03 | | D41409J | 1 | | *1 | 115-199 |
| 0247 | 24 | | GK | | 3-5 | 34-21-31 | D00319F | | D05 | | D41409J | 2 | | *U | 001-099 |
| 0247 | 24 | | GK | | 3-4 | 34-21-31 | D00319F | | D05 | | D41409J | 2 | | *1 | 115-199 |
| 0248 | 24 | | GK | | 2-8 | 34-21-31 | D00321F | | D05 | | D41409J | 2 | | *U | 001-099 |
| 0248 | 24 | | GK | | 2-8 | 34-21-31 | D00321F | | D05 | | D41409J | 2 | | *1 | 115-199 |
| 0250 | 24 | | GK | | 3-5 | 34-21-31 | D00319F | | C04 | | D41409J | 3 | | *U | 001-099 |
| 0250 | 24 | | GK | | 3-4 | 34-21-31 | D00319F | | C04 | | D41409J | 3 | | *1 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 74

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0251 | 24 | | GK | | 2-8 | 34-21-31 | D00321F | | C04 | | D41409J | 3 | | *U | 001-099 |
| 0251 | 24 | | GK | | 2-8 | 34-21-31 | D00321F | | C04 | | D41409J | 3 | | *1 | 115-199 |
| 0253 | 24 | | GK | | 3-9 | 34-21-21 | D00319D | | E05 | | D41369J | 12 | | *G | 001-099 |
| 0253 | 24 | | GK | | 3-11 | 34-21-21 | D00319D | | E05 | | D41369J | 12 | | *G | 115-199 |
| 0254 | 24 | | GK | | 5-1 | 34-21-21 | D00321D | | E05 | | D41369J | 12 | | *G | 001-099 |
| 0254 | 24 | | GK | | 5-3 | 34-21-21 | D00321D | | E05 | | D41369J | 12 | | *G | 115-199 |
| 0256 | 24 | | GK | | 3-9 | 34-21-21 | D00319D | | E09 | | D41369J | 10 | | *G | 001-099 |
| 0256 | 24 | | GK | | 3-11 | 34-21-21 | D00319D | | E09 | | D41369J | 10 | | *G | 115-199 |
| 0257 | 24 | | GK | | 5-1 | 34-21-21 | D00321D | | E09 | | D41369J | 10 | | *G | 001-099 |
| 0257 | 24 | | GK | | 5-3 | 34-21-21 | D00321D | | E09 | | D41369J | 10 | | *G | 115-199 |
| 0259 | 24 | | GK | | 3-9 | 34-21-21 | D00319D | | E02 | | D41369J | 11 | | *G | 001-099 |
| 0259 | 24 | | GK | | 3-11 | 34-21-21 | D00319D | | E02 | | D41369J | 11 | | *G | 115-199 |
| 0260 | 24 | | GK | | 5-1 | 34-21-21 | D00321D | | E02 | | D41369J | 11 | | *G | 001-099 |
| 0260 | 24 | | GK | | 5-3 | 34-21-21 | D00321D | | E02 | | D41369J | 11 | | *G | 115-199 |
| 0262 | 22 | | GA | | 3-2 | 24-33-12 | D41660J | | 10 | | TB0207Y | A012 | BJ | | 001, 003-099 |
| 0262 | 22 | | GA | | 3-3 | 24-33-12 | D41660J | | 10 | | TB0207Y | A012 | BJ | | 002 |
| 0264 | 22 | | GA | | 2-10 | 24-33-12 | D41844J | | 18 | | TB0207Y | A012 | BJ | | 001, 003-099 |
| 0264 | 22 | | GA | | 2-11 | 24-33-12 | D41844J | | 18 | | TB0207Y | A012 | BJ | | 002 |
| 0265 | 24 | | GK | | 3-6 | 24-33-12 | D00319D | | G10 | | TB0207Y | A012 | BJ | | 001, 003-099, 115-199 |
| 0265 | 24 | | GK | | 3-7 | 24-33-12 | D00319D | | G10 | | TB0207Y | A012 | BJ | | 002 |
| 0266 | 24 | | GK | | 4-10 | 24-33-12 | D00321D | | G10 | | TB0207Y | A012 | BJ | | 001, 003-099 |
| 0266 | 24 | | GK | | 4-11 | 24-33-12 | D00321D | | G10 | | TB0207Y | A012 | BJ | | 002 |
| 0266 | 24 | | GK | | 4-9 | 24-33-12 | D00321D | | G10 | | TB0207Y | A012 | BJ | | 115-199 |
| 0267 | 22 | | GA | | 2-9 | 24-33-12 | D41660J | | 23 | | TB0207Y | C028 | BJ | | 001-099 |
| 0268 | 22 | | GA | | 3-4 | 24-33-12 | D41660J | | 34 | | D41844J | 17 | | | 001-099 |
| 0269 | 22 | | GA | | 2-10 | 24-33-12 | D00319F | | E02 | | TB0207Y | C028 | BJ | | 001-099 |
| 0269 | 24 | | GK | | 2-5 | 24-33-12 | D00319F | | E02 | | GD02207 | DC.. | 2 | | 115-199 |
| 0270 | 22 | | GA | | 4-2 | 24-33-12 | D00321F | | E02 | | TB0207Y | C028 | BJ | | 001, 003-099 |
| 0270 | 22 | | GA | | 4-3 | 24-33-12 | D00321F | | E02 | | TB0207Y | C028 | BJ | | 002 |
| 0270 | 24 | | GK | | 3-6 | 24-33-12 | D00321F | | E02 | | GD02215 | DC.. | 2 | | 115-199 |
| 0272 | 24 | | GK | | 3-6 | 22-24-11 | D00319F | | E04 | | D41451J | 41 | | *H | ALL |
| 0273 | 24 | | GK | | 2-9 | 22-24-11 | D00321F | | E04 | | D41451J | 41 | | *H | ALL |
| 0276 | 24 | | GK | | 2-9 | 27-61-12 | D00319D | | C11 | | D42185J | 3 | | *O | 001-099 |
| 0276 | 24 | | GK | | 2-9 | 27-61-12 | D00319D | | C11 | | D42185J | 3 | | *1 | 115-199 |
| 0277 | 24 | | GK | | 3-7 | 27-61-12 | D00321D | | C11 | | D42185J | 3 | | *O | 001-099 |
| 0277 | 24 | | GK | | 3-8 | 27-61-12 | D00321D | | C11 | | D42185J | 3 | | *1 | 115-199 |
| 0279 | 24 | | GK | | 2-9 | 27-21-12 | D00319D | | C13 | | D42185J | 1 | | *O | 001-099 |
| 0279 | 24 | | GK | | 2-9 | 27-21-12 | D00319D | | C13 | | D42185J | 1 | | *1 | 115-199 |
| 0280 | 24 | | GK | | 3-7 | 27-21-12 | D00321D | | C13 | | D42185J | 1 | | *O | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 75

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0280 | 24 | | GK | | 3-8 | 27-21-12 | D00321D | | C13 | | D42185J | 1 | | *1 | 115-199 |
| 0283 | 24 | | GK | | 2-7 | 27-41-11 | D00319E | | B12 | | D42185J | 6 | | *O | 001-099 |
| 0283 | 24 | | GK | | 2-8 | 27-41-11 | D00319E | | B12 | | D42185J | 6 | | *1 | 115-199 |
| 0284 | 24 | | GK | | 3-8 | 27-41-11 | D00321A | | D11 | | D42185J | 5 | | *O | 001-099 |
| 0284 | 24 | | GK | | 3-9 | 27-41-11 | D00321A | | D11 | | D42185J | 5 | | *1 | 115-199 |
| 0285 | 24 | | GK | | 3-6 | 27-41-11 | D00321E | | B12 | | D42185J | 6 | | *O | 001-099 |
| 0285 | 24 | | GK | | 3-7 | 27-41-11 | D00321E | | B12 | | D42185J | 6 | | *1 | 115-199 |
| 0286 | 24 | | GK | | 2-8 | 27-41-11 | D00319A | | D11 | | D42185J | 5 | | *O | 001-099 |
| 0286 | 24 | | GK | | 2-9 | 27-41-11 | D00319A | | D11 | | D42185J | 5 | | *1 | 115-199 |
| 0288 | 24 | | GK | | 2-7 | 27-31-12 | D00319E | | G15 | | D42185J | 2 | | *O | 001-099 |
| 0288 | 24 | | GK | | 2-8 | 27-31-12 | D00319E | | G15 | | D42185J | 2 | | *1 | 115-199 |
| 0289 | 24 | | GK | | 3-6 | 27-31-12 | D00321E | | G15 | | D42185J | 2 | | *O | 001-099 |
| 0289 | 24 | | GK | | 3-7 | 27-31-12 | D00321E | | G15 | | D42185J | 2 | | *1 | 115-199 |
| 0290 | 24 | | GK | | 3-10 | 27-09-14 | D00321E | | A10 | | TB0207Y | A041 | BJ | | 001, 003-099, 115-199 |
| 0290 | 24 | | GK | | 3-11 | 27-09-14 | D00321E | | A10 | | TB0207Y | A041 | BJ | | 002 |
| 0291 | 24 | | GK | | 3-8 | 27-09-14 | D00321F | | D03 | | TB0207Y | C041 | BJ | | 001, 003-099 |
| 0291 | 24 | | GK | | 3-9 | 27-09-14 | D00321F | | D03 | | TB0207Y | C041 | BJ | | 002, 115-199 |
| 0292 | 24 | | GK | | 2-5 | 27-09-14 | D00319E | | A10 | | TB0207Y | A041 | BJ | | 001, 003-099 |
| 0292 | 24 | | GK | | 2-6 | 27-09-14 | D00319E | | A10 | | TB0207Y | A041 | BJ | | 002, 115-199 |
| 0293 | 24 | | GK | | 2-4 | 27-09-14 | D00319F | | D03 | | TB0207Y | C041 | BJ | | 001-099 |
| 0293 | 24 | | GK | | 2-5 | 27-09-14 | D00319F | | D03 | | TB0207Y | C041 | BJ | | 115-199 |
| 0298 | 22 | | GA | | 4-1 | 35-11-13 | D40704J | | 5 | | D41369J | 37 | | | 001-099 |
| 0301 | 24 | | GK | | 3-3 | 35-11-13 | D00319A | | F09 | | TB0207Y | A100 | BJ | | 001-099 |
| 0301 | 24 | | GK | | 3-4 | 35-11-13 | D00319A | | F09 | | TB0207Y | A100 | BJ | | 115-199 |
| 0302 | 24 | | GK | | 2-10 | 35-11-13 | D00321A | | F09 | | TB0207Y | A100 | BJ | | ALL |
| 0304 | 24 | | GK | | 2-9 | 35-21-11 | D00321F | | F06 | | D41451J | 47 | | *H | ALL |
| 0305 | 24 | | GK | | 3-6 | 35-21-11 | D00319F | | F06 | | D41451J | 47 | | *H | ALL |
| 0311 | 24 | | GK | | 2-10 | 76-11-11 | D00321B | | D14 | | D41738J | 44 | | *R | 001-099 |
| 0311 | 24 | | GK | | 2-9 | 76-11-11 | D00321B | | D14 | | TB0207Y | C100 | BJ | | 115-199 |
| 0312 | 24 | | GK | | 4-1 | 76-11-11 | D00319B | | D14 | | D41738J | 44 | | *R | 001-099 |
| 0312 | 24 | | GK | | 3-3 | 76-11-11 | D00319B | | D14 | | TB0207Y | C100 | BJ | | 115-199 |
| 0314 | 24 | | GK | | 4-1 | 76-11-11 | D00319B | | F13 | | D41738J | 45 | | *R | 001-099 |
| 0314 | 24 | | GK | | 4-2 | 76-11-11 | D00319B | | F13 | | D41738J | 45 | | *R | 115-199 |
| 0315 | 24 | | GK | | 2-10 | 76-11-11 | D00321B | | F13 | | D41738J | 45 | | *R | 001-099 |
| 0315 | 24 | | GK | | 2-11 | 76-11-11 | D00321B | | F13 | | D41738J | 45 | | *R | 115-199 |
| 0319 | 24 | | GK | | 3-6 | 76-11-12 | D00321B | | D15 | | D41776J | 31 | | *V | ALL |
| 0320 | 24 | | GK | | 3-1 | 76-11-12 | D00319B | | D15 | | D41776J | 31 | | *V | ALL |
| 0322 | 24 | | GK | | 3-1 | 76-11-12 | D00319B | | J03 | | D41776J | 32 | | *V | 001-099 |
| 0322 | 24 | | GK | | 2-11 | 76-11-12 | D00319B | | J03 | | TB0207Y | C083 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 76

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0323 | 24 | | GK | | 3-6 | 76-11-12 | D00321B | J03 | | | D41776J | 32 | | *V | 001-099 |
| 0323 | 24 | | GK | | 3-2 | 76-11-12 | D00321B | J03 | | | TB0207Y | C083 | BJ | | 115-199 |
| 0324 | 24 | | GK | | 3-3 | 78-36-11 | D00321B | F03 | | | D41734J | 24 | | *P | ALL |
| 0325 | 24 | | GK | | 3-3 | 78-36-11 | D00321B | G03 | | | D41734J | 22 | | *P | ALL |
| 0326 | 24 | | GK | | 2-10 | 78-36-11 | D00319B | G03 | | | D41734J | 22 | | *P | ALL |
| 0327 | 24 | | GK | | 2-10 | 78-36-11 | D00319B | F03 | | | D41734J | 24 | | *P | ALL |
| 0328 | 24 | | GK | | 3-6 | 78-36-21 | D00321D | F12 | | | D41736J | 18 | | *Q | ALL |
| 0329 | 24 | | GK | | 3-6 | 78-36-21 | D00321D | F14 | | | D41736J | 19 | | *Q | ALL |
| 0330 | 24 | | GK | | 3-3 | 78-36-21 | D00319D | F14 | | | D41736J | 19 | | *Q | 001-099 |
| 0330 | 24 | | GK | | 3-2 | 78-36-21 | D00319D | F14 | | | D41736J | 19 | | *Q | 115-199 |
| 0331 | 24 | | GK | | 3-3 | 78-36-21 | D00319D | F12 | | | D41736J | 18 | | *Q | 001-099 |
| 0331 | 24 | | GK | | 3-2 | 78-36-21 | D00319D | F12 | | | D41736J | 18 | | *Q | 115-199 |
| 0341 | 24 | | GK | | 4-1 | 49-61-11 | D00321B | A13 | | | D41660J | 12 | | *K | 001-099 |
| 0341 | 24 | | GK | | 4-2 | 49-61-11 | D00321B | A13 | | | D41660J | 12 | | *K | 115-199 |
| 0342 | 24 | | GK | | 2-9 | 49-61-11 | D00319B | A13 | | | D41660J | 12 | | *K | ALL |
| 0344 | 24 | | GK | | 4-0 | 32-42-12 | D00319A | G06 | | | D42041J | 24 | | *Y | 001-099 |
| 0344 | 24 | | GK | | 4-0 | 32-42-12 | D00319A | G06 | | | D42041J | 24 | | *1 | 115-199 |
| 0345 | 24 | | GK | | 5-5 | 32-42-12 | D00321A | G06 | | | D42041J | 24 | | *Y | 001-099 |
| 0345 | 24 | | GK | | 5-5 | 32-42-12 | D00321A | G06 | | | D42041J | 24 | | *1 | 115-199 |
| 0348 | 24 | | GK | | 3-10 | 24-33-12 | D41660J | 33 | | | D40904J | 6 | | | 001-099 |
| 0350 | 24 | | GK | | 2-6 | 24-33-12 | D41660J | 14 | | *K | D00319F | B03 | | | 001-099 |
| 0350 | 24 | | GK | | 2-7 | 24-33-12 | D00319F | B03 | | | D41660J | 30 | | *K | 115-199 |
| 0352 | 24 | | GK | | 3-11 | 24-33-12 | D41660J | 14 | | *K | D00321F | B03 | | | 001-099 |
| 0352 | 24 | | GK | | 3-11 | 24-33-12 | D00321F | B03 | | | D41660J | 30 | | *K | 115-199 |
| 0353 | 24 | | GK | | 2-4 | 24-11-11 | TB0207B | A061 | 2 | | TB0207Z | 78 | BJ | | 001, 003-099 |
| 0353 | 24 | | GK | | 2-5 | 24-11-11 | TB0207B | A061 | 2 | | TB0207Z | 78 | BJ | | 002 |
| 0353 | 24 | | GK | | 2-7 | 24-11-11 | TB0207B | A061 | 2 | | TB0207Z | 78 | BJ | | 115-199 |
| 0354 | 24 | | GK | | 2-4 | 24-11-21 | TB0207Z | 77 | BJ | | TB0207B | A062 | 2 | | 001, 003-099 |
| 0354 | 24 | | GK | | 2-5 | 24-11-21 | TB0207Z | 77 | BJ | | TB0207B | A062 | 2 | | 002 |
| 0354 | 24 | | GK | | 2-7 | 24-11-21 | TB0207B | A062 | 2 | | TB0207Z | 77 | BJ | | 115-199 |
| 0358 | 22 | | GA | | 4-7 | 35-11-13 | D41369J | 19 | | | TB0207Y | A100 | BJ | | 115-199 |
| 0359 | 22 | | GA | | 4-7 | 35-11-13 | D41369J | 20 | | | GD02213 | DC.. | 2 | | 115-199 |
| 0361 | 24 | | GK | | 2-5 | 34-12-12 | D00319F | E05 | | | D41879J | 39 | | *Z | 001-099 |
| 0361 | 24 | | GK | | 2-6 | 34-12-12 | D00319F | E05 | | | D41879J | 39 | | *Z | 115-199 |
| 0362 | 24 | | GK | | 3-10 | 34-12-12 | D00319B | C15 | | | D41867J | 30 | | *Y | 001-099 |
| 0362 | 24 | | GK | | 3-11 | 34-12-12 | D00319B | C15 | | | D41867J | 30 | | *Y | 115-199 |
| 0363 | 24 | | GK | | 3-9 | 34-12-22 | D00321F | E05 | | | D41879J | 39 | | *Z | 001-099 |
| 0363 | 24 | | GK | | 3-10 | 34-12-22 | D00321F | E05 | | | D41879J | 39 | | *Z | 115-199 |
| 0368 | 24 | | GK | | 5-3 | 34-12-22 | D00321B | C15 | | | D41867J | 30 | | *Y | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 77

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0369 | 24 | | GK | | 2-8 | 21-33-12 | D00319A | F13 | | | D41879J | 43 | | *Z | 001-099 |
| 0369 | 24 | | GK | | 2-9 | 21-33-12 | D00319A | F13 | | | D41879J | 43 | | *Z | 115-199 |
| 0370 | 24 | | GK | | 4-1 | 21-33-12 | D00321A | F13 | | | D41879J | 43 | | *Z | ALL |
| 0373 | 24 | | GK | | 2-6 | 22-14-31 | D00319E | A09 | | | D41879J | 19 | | *Z | 001-099 |
| 0373 | 24 | | GK | | 2-7 | 22-14-31 | D00319E | A09 | | | D41879J | 19 | | *Z | 115-199 |
| 0374 | 24 | | GK | | 3-8 | 22-14-31 | D00319D | G07 | | | D41409J | 12 | | *U | 001-099 |
| 0374 | 24 | | GK | | 3-7 | 22-14-31 | D00319D | G07 | | | D41409J | 12 | | *1 | 115-199 |
| 0375 | 24 | | GK | | 3-11 | 22-14-31 | D00321E | A09 | | | D41879J | 19 | | *Z | ALL |
| 0376 | 24 | | GK | | 2-11 | 22-14-31 | D00321D | G07 | | | D41409J | 12 | | *U | 001-099 |
| 0376 | 24 | | GK | | 2-11 | 22-14-31 | D00321D | G07 | | | D41409J | 12 | | *1 | 115-199 |
| 0378 | 24 | | GK | | 2-11 | 34-21-11 | D00319A | G08 | | | D41317J | 46 | | *F | 001-099 |
| 0378 | 24 | | GK | | 3-0 | 34-21-11 | D00319A | G08 | | | D41317J | 46 | | *F | 115-199 |
| 0379 | 24 | | GK | | 4-4 | 34-21-11 | D00321A | G08 | | | D41317J | 46 | | *F | ALL |
| 0381 | 24 | | GK | | 2-11 | 34-21-11 | D00319A | G01 | | | D41317J | 47 | | *F | 001-099 |
| 0381 | 24 | | GK | | 3-0 | 34-21-11 | D00319A | G01 | | | D41317J | 47 | | *F | 115-199 |
| 0382 | 24 | | GK | | 4-4 | 34-21-11 | D00321A | G01 | | | D41317J | 47 | | *F | ALL |
| 0384 | 24 | | GK | | 2-11 | 34-21-11 | D00319A | G05 | | | D41317J | 48 | | *F | 001-099 |
| 0384 | 24 | | GK | | 3-0 | 34-21-11 | D00319A | G05 | | | D41317J | 48 | | *F | 115-199 |
| 0385 | 24 | | GK | | 4-4 | 34-21-11 | D00321A | G05 | | | D41317J | 48 | | *F | ALL |
| 0386 | 24 | | GK | | 4-8 | 32-61-21 | D42093J | 9 | | | TB0207Y | A021 | BJ | | 001, 003-099 |
| 0386 | 24 | | GK | | 4-9 | 32-61-21 | D42093J | 9 | | | TB0207Y | A021 | BJ | | 002 |
| 0386 | 24 | | GK | | 4-10 | 32-61-21 | D42093J | 9 | | | TB0207Y | A021 | BJ | | 115-199 |
| 0387 | 24 | | GK | | 4-2 | 32-61-21 | D00321F | C05 | | | TB0207Y | A021 | BJ | | 001, 003-099, 115-199 |
| 0387 | 24 | | GK | | 4-3 | 32-61-21 | D00321F | C05 | | | TB0207Y | A021 | BJ | | 002 |
| 0388 | 24 | | GK | | 2-11 | 32-61-21 | D41867J | 3 | | | TB0207Y | A021 | BJ | | 001, 003-099 |
| 0388 | 24 | | GK | | 3-0 | 32-61-21 | D41867J | 3 | | | TB0207Y | A021 | BJ | | 002 |
| 0388 | 24 | | GK | | 3-1 | 32-61-21 | D41867J | 3 | | | TB0207Y | A021 | BJ | | 115-199 |
| 0389 | 24 | | GK | | 2-9 | 32-61-21 | D00319F | C05 | | | TB0207Y | A021 | BJ | | 001, 003-099 |
| 0389 | 24 | | GK | | 2-10 | 32-61-21 | D00319F | C05 | | | TB0207Y | A021 | BJ | | 002, 115-199 |
| 0391 | 24 | | GK | | 4-2 | 32-61-21 | D00321F | D06 | | | TB0207Y | C021 | BJ | | 001, 003-099, 115-199 |
| 0391 | 24 | | GK | | 4-3 | 32-61-21 | D00321F | D06 | | | TB0207Y | C021 | BJ | | 002 |
| 0392 | 24 | | GK | | 2-11 | 32-61-21 | D41867J | 4 | | | TB0207Y | C021 | BJ | | 001, 003-099 |
| 0392 | 24 | | GK | | 3-0 | 32-61-21 | D41867J | 4 | | | TB0207Y | C021 | BJ | | 002 |
| 0392 | 24 | | GK | | 3-1 | 32-61-21 | D41867J | 4 | | | TB0207Y | C021 | BJ | | 115-199 |
| 0393 | 24 | | GK | | 2-9 | 32-61-21 | D00319F | D06 | | | TB0207Y | C021 | BJ | | 001, 003-099 |
| 0393 | 24 | | GK | | 2-10 | 32-61-21 | D00319F | D06 | | | TB0207Y | C021 | BJ | | 002, 115-199 |
| 0394 | 24 | | GK | | 4-8 | 32-61-21 | D42093J | 7 | | | TB0207Y | A022 | BJ | | 001, 003-099 |
| 0394 | 24 | | GK | | 4-9 | 32-61-21 | D42093J | 7 | | | TB0207Y | A022 | BJ | | 002 |
| 0394 | 24 | | GK | | 4-10 | 32-61-21 | D42093J | 7 | | | TB0207Y | A022 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 78

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0395 | 24 | | GK | | 4-2 | 32-61-21 | D00321F | | C07 | | TB0207Y | A022 | BJ | | 001, 003-099, 115-199 | |
| 0395 | 24 | | GK | | 4-3 | 32-61-21 | D00321F | | C07 | | TB0207Y | A022 | BJ | | 002 | |
| 0396 | 24 | | GK | | 2-11 | 32-61-21 | D41867J | | 5 | | TB0207Y | A022 | BJ | | 001, 003-099 | |
| 0396 | 24 | | GK | | 3-0 | 32-61-21 | D41867J | | 5 | | TB0207Y | A022 | BJ | | 002 | |
| 0396 | 24 | | GK | | 3-1 | 32-61-21 | D41867J | | 5 | | TB0207Y | A022 | BJ | | 115-199 | |
| 0397 | 24 | | GK | | 2-9 | 32-61-21 | D00319F | | C07 | | TB0207Y | A022 | BJ | | 001, 003-099 | |
| 0397 | 24 | | GK | | 2-10 | 32-61-21 | D00319F | | C07 | | TB0207Y | A022 | BJ | | 002, 115-199 | |
| 0398 | 24 | | GK | | 3-1 | 32-61-21 | D42073J | | 9 | | TB0207Y | C024 | BJ | | 001, 003-099 | |
| 0398 | 24 | | GK | | 3-2 | 32-61-21 | D42073J | | 9 | | TB0207Y | C024 | BJ | | 002, 115-199 | |
| 0399 | 24 | | GK | | 4-5 | 32-61-21 | D00321D | | G13 | | TB0207Y | C024 | BJ | | 001, 003-099, 115-199 | |
| 0399 | 24 | | GK | | 4-6 | 32-61-21 | D00321D | | G13 | | TB0207Y | C024 | BJ | | 002 | |
| 0400 | 24 | | GK | | 2-7 | 32-61-21 | D41879J | | 1 | | TB0207Y | C024 | BJ | | 001, 003-099, 115-199 | |
| 0400 | 24 | | GK | | 2-8 | 32-61-21 | D41879J | | 1 | | TB0207Y | C024 | BJ | | 002 | |
| 0401 | 24 | | GK | | 3-0 | 32-61-21 | D00319D | | G13 | | TB0207Y | C024 | BJ | | 001, 003-099 | |
| 0401 | 24 | | GK | | 3-1 | 32-61-21 | D00319D | | G13 | | TB0207Y | C024 | BJ | | 002, 115-199 | |
| 0402 | 24 | | GK | | 3-1 | 32-61-21 | D42073J | | 8 | | TB0207Y | C022 | BJ | | 001, 003-099 | |
| 0402 | 24 | | GK | | 3-2 | 32-61-21 | D42073J | | 8 | | TB0207Y | C022 | BJ | | 002, 115-199 | |
| 0403 | 24 | | GK | | 4-5 | 32-61-21 | D00321D | | F08 | | TB0207Y | C022 | BJ | | 001, 003-099, 115-199 | |
| 0403 | 24 | | GK | | 4-6 | 32-61-21 | D00321D | | F08 | | TB0207Y | C022 | BJ | | 002 | |
| 0404 | 24 | | GK | | 2-7 | 32-61-21 | D41879J | | 2 | | TB0207Y | C022 | BJ | | 001, 003-099, 115-199 | |
| 0404 | 24 | | GK | | 2-8 | 32-61-21 | D41879J | | 2 | | TB0207Y | C022 | BJ | | 002 | |
| 0405 | 24 | | GK | | 3-0 | 32-61-21 | D00319D | | F08 | | TB0207Y | C022 | BJ | | 001, 003-099 | |
| 0405 | 24 | | GK | | 3-1 | 32-61-21 | D00319D | | F08 | | TB0207Y | C022 | BJ | | 002, 115-199 | |
| 0406 | 24 | | GK | | 3-1 | 32-61-21 | D42073J | | 7 | | TB0207Y | A023 | BJ | | 001, 003-099 | |
| 0406 | 24 | | GK | | 3-2 | 32-61-21 | D42073J | | 7 | | TB0207Y | A023 | BJ | | 002, 115-199 | |
| 0407 | 24 | | GK | | 4-5 | 32-61-21 | D00321D | | F06 | | TB0207Y | A023 | BJ | | 001, 003-099, 115-199 | |
| 0407 | 24 | | GK | | 4-6 | 32-61-21 | D00321D | | F06 | | TB0207Y | A023 | BJ | | 002 | |
| 0408 | 24 | | GK | | 2-7 | 32-61-21 | D41879J | | 3 | | TB0207Y | A023 | BJ | | 001, 003-099, 115-199 | |
| 0408 | 24 | | GK | | 2-8 | 32-61-21 | D41879J | | 3 | | TB0207Y | A023 | BJ | | 002 | |
| 0409 | 24 | | GK | | 3-0 | 32-61-21 | D00319D | | F06 | | TB0207Y | A023 | BJ | | 001, 003-099 | |
| 0409 | 24 | | GK | | 3-1 | 32-61-21 | D00319D | | F06 | | TB0207Y | A023 | BJ | | 002, 115-199 | |
| 0412 | 24 | | GK | | 3-8 | 32-46-11 | D00321E | | H01 | | D41664J | 1 | | *L | 115-199 | |
| 0413 | 24 | | GK | | 2-9 | 32-46-11 | D00319E | | H01 | | D41664J | 1 | | *L | 115-199 | |
| 0415 | 24 | | GK | | 3-11 | 32-46-11 | D00321A | | F10 | | D41664J | 32 | | *L | 115-199 | |
| 0416 | 24 | | GK | | 2-11 | 32-46-11 | D00319A | | F10 | | D41664J | 32 | | *L | 115-199 | |
| 0418 | 24 | | GK | | 3-11 | 32-46-11 | D00321A | | E02 | | D41664J | 3 | | *L | 115-199 | |
| 0419 | 24 | | GK | | 2-11 | 32-46-11 | D00319A | | E02 | | D41664J | 3 | | *L | 115-199 | |
| 0421 | 24 | | GK | | 3-9 | 32-46-11 | D00321B | | E03 | | D41664J | 4 | | *L | 115-199 | |
| 0422 | 24 | | GK | | 2-10 | 32-46-11 | D00319B | | E03 | | D41664J | 4 | | *L | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 79

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|--------------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | |
| 0424 | 24 | | GK | | 3-9 | 32-46-11 | D00321B | E02 | | | D41664J | 5 | | *L | 115-199 | |
| 0425 | 24 | | GK | | 2-10 | 32-46-11 | D00319B | E02 | | | D41664J | 5 | | *L | 115-199 | |
| 0427 | 24 | | GK | | 3-10 | 32-46-11 | D00321D | D07 | | | D41664J | 6 | | *L | 115-199 | |
| 0428 | 24 | | GK | | 2-11 | 32-46-11 | D00319D | D07 | | | D41664J | 6 | | *L | 115-199 | |
| 0430 | 24 | | GK | | 3-10 | 32-46-11 | D00321D | D15 | | | D41664J | 7 | | *L | 115-199 | |
| 0431 | 24 | | GK | | 2-11 | 32-46-11 | D00319D | D15 | | | D41664J | 7 | | *L | 115-199 | |
| 0433 | 24 | | GK | | 3-10 | 32-46-11 | D00321D | D06 | | | D41664J | 8 | | *L | 115-199 | |
| 0434 | 24 | | GK | | 2-11 | 32-46-11 | D00319D | D06 | | | D41664J | 8 | | *L | 115-199 | |
| 0439 | 22 | | GA | | 3-6 | 29-11-22 | D42185J | 28 | | | TB0207Z | 13 | BJ | | 001, 003-099 | |
| 0439 | 22 | | GA | | 3-7 | 29-11-22 | D42185J | 28 | | | TB0207Z | 13 | BJ | | 002, 115-199 | |
| 0440 | 22 | | GA | | 3-1 | 29-11-22 | D42185J | 27 | | | TB0207Y | A024 | BJ | | 001, 003-099 | |
| 0440 | 22 | | GA | | 3-2 | 29-11-22 | D42185J | 27 | | | TB0207Y | A024 | BJ | | 002, 115-199 | |
| 0441 | 24 | | GK | | 3-2 | 29-22-11 | D41720J | 17 | | | TB0207Z | 103 | BJ | | 001-099 | |
| 0441 | 24 | | GK | | 3-6 | 29-22-11 | D41720J | 17 | | | TB0207Z | 27 | BJ | | 115-199 | |
| 0443 | 24 | | GK | | 2-7 | 79-31-11 | D00321E | E04 | | | TB0207Y | A095 | BJ | | 001-099 | |
| 0443 | 24 | | GK | | 3-1 | 79-31-11 | D00321E | E04 | | | TB0207Z | 77 | BJ | | 115-199 | |
| 0444 | 24 | | GK | | 2-8 | 79-31-11 | D00319F | G10 | | | TB0207Z | 78 | BJ | | 001-099 | |
| 0444 | 24 | | GK | | 2-9 | 79-31-11 | D00319F | G10 | | | TB0207Z | 78 | BJ | | 115-199 | |
| 0445 | 22 | | GA | | 3-1 | 28-42-11 | D41720J | 1 | | | TB0207Y | A045 | BJ | | 001-099 | |
| 0445 | 22 | | GA | | 3-0 | 28-42-11 | D41720J | 1 | | | TB0207Y | A045 | BJ | | 115-199 | |
| 0446 | 24 | | GK | | 4-0 | 28-42-11 | D00321D | G08 | | | TB0207Y | A045 | BJ | | ALL | |
| 0447 | 24 | | GK | | 2-7 | 28-42-11 | D00319D | G08 | | | TB0207Y | A045 | BJ | | 001-099 | |
| 0447 | 24 | | GK | | 2-8 | 28-42-11 | D00319D | G08 | | | TB0207Y | A045 | BJ | | 115-199 | |
| 0451 | 24 | | GK | | 3-3 | 73-21-11 | D00321B | H08 | | | D41734J | 42 | | *P | 115-199 | |
| 0452 | 24 | | GK | | 2-10 | 73-21-11 | D00319B | H08 | | | D41734J | 42 | | *P | 115-199 | |
| 0453 | 22 | | GA | | 2-10 | 28-42-11 | D41698J | 12 | | | TB0207Y | A046 | BJ | | ALL | |
| 0455 | 24 | | GK | | 4-1 | 73-21-12 | D00319B | H06 | | | D41738J | 31 | | *R | 001-099 | |
| 0455 | 24 | | GK | | 4-2 | 73-21-12 | D00319B | H06 | | | D41738J | 31 | | *R | 115-199 | |
| 0456 | 24 | | GK | | 2-10 | 73-21-12 | D00321B | H06 | | | D41738J | 31 | | *R | 001-099 | |
| 0456 | 24 | | GK | | 2-11 | 73-21-12 | D00321B | H06 | | | D41738J | 31 | | *R | 115-199 | |
| 0461 | 24 | | GK | | 4-0 | 28-42-11 | D00321B | E07 | | | TB0207Y | A046 | BJ | | 001-099 | |
| 0461 | 24 | | GK | | 3-11 | 28-42-11 | D00321B | E07 | | | TB0207Y | A046 | BJ | | 115-199 | |
| 0462 | 24 | | GK | | 3-2 | 73-21-21 | D00319D | H04 | | | D41736J | 36 | | *Q | 115-199 | |
| 0463 | 24 | | GK | | 3-6 | 73-21-21 | D00321D | H04 | | | D41736J | 36 | | *Q | 115-199 | |
| 0465 | 24 | | GK | | 3-3 | 73-21-22 | D00319D | K09 | | | D41776J | 20 | | *V | 001-099 | |
| 0465 | 24 | | GK | | 3-2 | 73-21-22 | D00319D | K09 | | | D41776J | 20 | | *V | 115-199 | |
| 0466 | 24 | | GK | | 3-6 | 73-21-22 | D00321D | K09 | | | D41776J | 20 | | *V | ALL | |
| 0471 | 24 | | GK | | 3-4 | 75-31-11 | D00321D | J02 | | | D41788J | CAP | Y | | 115-199 | |
| 0472 | 24 | | GK | | 4-5 | 75-31-11 | D00319D | J02 | | | D41788J | CAP | Y | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 80

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0475 | 24 | | GK | | 6-0 | 75-31-11 | D00321A | H05 | | | D41772J | CAP | Y | | 115-199 |
| 0476 | 24 | | GK | | 4-2 | 75-31-11 | D00319A | H05 | | | D41772J | CAP | Y | | 115-199 |
| 0486 | 24 | | GK | | 2-7 | 28-42-11 | D00319B | E07 | | | TB0207Y | A046 | BJ | | ALL |
| 0493 | 24 | | GK | | 3-3 | 78-36-11 | D00321B | H07 | | | D41734J | 25 | | *P | ALL |
| 0494 | 24 | | GK | | 2-10 | 78-36-11 | D00319B | H07 | | | D41734J | 25 | | *P | ALL |
| 0503 | 24 | | GK | | 2-10 | 26-11-11 | D41738J | 6 | | | TB0207A | A087 | 2 | | 001, 003-099 |
| 0503 | 24 | | GK | | 2-11 | 26-11-11 | D41738J | 6 | | | TB0207A | A087 | 2 | | 002 |
| 0503 | 24 | | GK | | 3-0 | 26-11-11 | D41738J | 6 | | | TB0207A | A087 | 2 | | 115-199 |
| 0510 | 24 | | GK | | 3-6 | 78-36-21 | D00321D | H07 | | | D41736J | 24 | | *Q | ALL |
| 0511 | 24 | | GK | | 3-3 | 78-36-21 | D00319D | H07 | | | D41736J | 24 | | *Q | 001-099 |
| 0511 | 24 | | GK | | 3-2 | 78-36-21 | D00319D | H07 | | | D41736J | 24 | | *Q | 115-199 |
| 0512 | 24 | | GK | | 3-7 | 26-17-11 | TB0207Y | C023 | BJ | | TB0207A | C087 | 2 | | 001, 003-099 |
| 0512 | 24 | | GK | | 3-9 | 26-17-11 | TB0207Y | C023 | BJ | | TB0207A | C087 | 2 | | 002, 115-199 |
| 0513 | 22 | | GA | | 3-2 | 27-18-11 | R10151 | B | \$ | | TB0207Y | A067 | BJ | | 001, 003-099, 115-199 |
| 0513 | 22 | | GA | | 3-3 | 27-18-11 | R10151 | B | \$ | | TB0207Y | A067 | BJ | | 002 |
| 0517 | 24 | | GK | | 3-5 | 80-11-11 | D00321F | D09 | | | D41764J | 18 | | *S | 001-099 |
| 0517 | 24 | | GK | | 4-7 | 80-11-11 | D00321F | D09 | | | D41764J | 18 | | *S | 115-199 |
| 0518 | 24 | | GK | | 2-6 | 80-11-11 | D00319F | D09 | | | D41764J | 18 | | *S | 001-099 |
| 0518 | 24 | | GK | | 3-4 | 80-11-11 | D00319F | D09 | | | D41764J | 18 | | *S | 115-199 |
| 0520 | 24 | | GK | | 3-7 | 80-11-11 | D00321B | H11 | | | D41764J | 19 | | *S | 001-099 |
| 0520 | 24 | | GK | | 4-10 | 80-11-11 | D00321B | H11 | | | D41764J | 19 | | *S | 115-199 |
| 0521 | 24 | | GK | | 2-7 | 80-11-11 | D00319B | H11 | | | D41764J | 19 | | *S | 001-099 |
| 0521 | 24 | | GK | | 3-5 | 80-11-11 | D00319B | H11 | | | D41764J | 19 | | *S | 115-199 |
| 0526 | 24 | | GK | | 3-1 | 31-41-19 | D00319B | D04 | | | TB0207Y | C092 | BJ | | 001, 003-099 |
| 0526 | 24 | | GK | | 3-2 | 31-41-19 | D00319B | D04 | | | TB0207Y | C092 | BJ | | 002 |
| 0526 | 24 | | GK | | 3-3 | 31-41-19 | D00319B | D04 | | | TB0207Y | C092 | BJ | | 115-199 |
| 0527 | 22 | | GA | | 2-1 | 27-18-11 | R10152 | B | \$ | | TB0207Y | A058 | BJ | | 001-099 |
| 0527 | 22 | | GA | | 2-2 | 27-18-11 | R10152 | B | \$ | | TB0207Y | A058 | BJ | | 115-199 |
| 0531 | 24 | | GK | | 3-0 | 80-11-21 | D00321D | K02 | | | D41774J | 17 | | *U | 001-099 |
| 0531 | 24 | | GK | | 3-1 | 80-11-21 | D00321D | K02 | | | D41774J | 17 | | *U | 115-199 |
| 0532 | 24 | | GK | | 3-9 | 80-11-21 | D00319D | K02 | | | D41774J | 17 | | *U | 001-099 |
| 0532 | 24 | | GK | | 4-3 | 80-11-21 | D00319D | K02 | | | D41774J | 17 | | *U | 115-199 |
| 0539 | 24 | | GK | | 4-9 | 31-41-19 | D00321B | D04 | | | D41065J | 3 | | *1 | 001-099 |
| 0539 | 24 | | GK | | 4-7 | 31-41-19 | D00321B | D04 | | | D41065J | 3 | | *1 | 115-199 |
| 0540 | 24 | | GK | | 3-5 | 31-41-19 | D00319A | E09 | | | D41065J | 3 | | *1 | 001-099 |
| 0540 | 24 | | GK | | 3-4 | 31-41-19 | D00319A | E09 | | | D41065J | 3 | | *1 | 115-199 |
| 0550 | 24 | | GK | | 2-9 | 31-41-19 | D00321A | E09 | | | TB0207Y | C092 | BJ | | 001, 003-099 |
| 0550 | 24 | | GK | | 2-10 | 31-41-19 | D00321A | E09 | | | TB0207Y | C092 | BJ | | 002, 115-199 |
| 0551 | 24 | | GK | | 2-7 | 31-41-11 | D00789 | 47 | | | TB0207Y | A052 | BJ | | 001, 003-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 81

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | | | | | | | | | | | | | | | |
| | | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | |
| 0551 | 24 | GK | | | 2-8 | 31-41-11 | D00789 | | | | TB0207Y | A052 | BJ | | 002 |
| 0551 | 24 | GK | | | 2-10 | 31-41-11 | D00789 | | | | TB0207Y | A052 | BJ | | 115-199 |
| 0552 | 24 | GK | | | 2-7 | 31-41-11 | D00789 | | | | TB0207Y | A055 | BJ | | 001, 003-099 |
| 0552 | 24 | GK | | | 2-8 | 31-41-11 | D00789 | | | | TB0207Y | A055 | BJ | | 002 |
| 0552 | 24 | GK | | | 2-10 | 31-41-11 | D00789 | | | | TB0207Y | A055 | BJ | | 115-199 |
| 0553 | 24 | GK | | | 3-3 | 31-31-61 | D41451J | | | | TB0207Y | A055 | BJ | | 001-099 |
| 0553 | 24 | GK | | | 3-4 | 31-31-21 | D41451J | | | | TB0207Y | A055 | BJ | | 115-199 |
| 0554 | 24 | GK | | | 2-7 | 31-41-21 | D00791 | | | | TB0207Y | A055 | BJ | | 001, 003-099 |
| 0554 | 24 | GK | | | 2-8 | 31-41-21 | D00791 | | | | TB0207Y | A055 | BJ | | 002 |
| 0554 | 24 | GK | | | 2-10 | 31-41-21 | D00791 | | | | TB0207Y | A055 | BJ | | 115-199 |
| 0555 | 24 | GK | | | 2-7 | 31-41-21 | D00791 | | | | TB0207Y | A052 | BJ | | 001, 003-099 |
| 0555 | 24 | GK | | | 2-8 | 31-41-21 | D00791 | | | | TB0207Y | A052 | BJ | | 002 |
| 0555 | 24 | GK | | | 2-10 | 31-41-21 | D00791 | | | | TB0207Y | A052 | BJ | | 115-199 |
| 0556 | 24 | GK | | | 2-4 | 27-18-11 | D41720J | | | | GD02211 | AC.. | 2 | | ALL |
| 0557 | 24 | GK | | | 2-9 | 27-18-11 | D41720J | | | | GD02208 | ST.. | 2 | | 001-099 |
| 0557 | 24 | GK | | | 2-10 | 27-18-11 | D41720J | | | | GD02208 | ST.. | 2 | | 115-199 |
| 0558 | 24 | GK | | | 2-6 | 27-18-11 | D41698J | | | | GD02209 | AC.. | 2 | | ALL |
| 0559 | 24 | GK | | | 2-6 | 27-18-11 | D41698J | | | | GD02208 | ST.. | 2 | | 001-099 |
| 0559 | 24 | GK | | | 2-7 | 27-18-11 | D41698J | | | | GD02208 | ST.. | 2 | | 115-199 |
| 0560 | 22 | GA | | | 3-2 | 31-41-11 | D40684J | | | | D00319C | | 1 | | 001-099 |
| 0561 | 22 | GA | | | 2-4 | 31-41-11 | D00319C | | | | GD02207 | AC.. | 2 | | 001-099 |
| 0561 | 22 | GA | | | 2-6 | 31-41-11 | D00319C | | | | GD02207 | AC.. | 2 | | 115-199 |
| 0562 | 22 | GA | | | 2-4 | 31-41-11 | D00319C | | | | GD02207 | DC.. | 2 | | 001-099 |
| 0562 | 22 | GA | | | 2-6 | 31-41-11 | D00319C | | | | GD02207 | DC.. | 2 | | 115-199 |
| 0563 | 22 | GA | | | 2-4 | 31-41-11 | D00319C | | | | GD02207 | AC.. | 2 | | 001-099 |
| 0563 | 22 | GA | | | 2-6 | 31-41-11 | D00319C | | | | GD02207 | AC.. | 2 | | 115-199 |
| 0574 | 24 | GK | | | 2-9 | 34-61-15 | D00319E | | K14 | | D41317J | | 21 | *F | 001-099 |
| 0574 | 24 | GK | | | 2-10 | 34-61-15 | D00319E | | K14 | | D41317J | | 21 | *F | 115-199 |
| 0575 | 24 | GK | | | 4-2 | 34-61-15 | D00321E | | K14 | | D41317J | | 21 | *F | ALL |
| 0577 | 24 | GK | | | 2-11 | 34-61-15 | D00319A | | G13 | | D41317J | | 22 | *F | 001-099 |
| 0577 | 24 | GK | | | 3-0 | 34-61-15 | D00319A | | G13 | | D41317J | | 22 | *F | 115-199 |
| 0578 | 24 | GK | | | 4-4 | 34-61-15 | D00321A | | G13 | | D41317J | | 22 | *F | ALL |
| 0582 | 24 | GK | | | 2-7 | 21-58-12 | D00321F | | K05 | | D40584J | | 52 | *C | 001-099 |
| 0582 | 24 | GK | | | 2-8 | 21-58-12 | D00321F | | K05 | | D40584J | | 52 | *C | 115-199 |
| 0583 | 24 | GK | | | 3-9 | 21-58-12 | D00319F | | K05 | | D40584J | | 52 | *C | ALL |
| 0585 | 24 | GK | | | 2-4 | 34-22-37 | D00319F | | A09 | | D42023J | | 19 | *1 | 001-099 |
| 0586 | 24 | GK | | | 3-3 | 34-22-37 | D00321F | | A09 | | D42023J | | 19 | *1 | 001-099 |
| 0586 | 24 | GK | | | 3-4 | 34-22-37 | D00321F | | A09 | | TB0207Y | A119 | BJ | | 115-199 |
| 0588 | 22 | GA | | | 3-1 | 31-41-21 | D00321C | | | 1 | D40704J | | 3 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 82

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0589 | 22 | | GA | | 2-4 | 31-41-21 | D00321C | | 4 | | GD02214 | AC.. | 2 | | ALL |
| 0590 | 22 | | GA | | 2-4 | 31-41-21 | D00321C | | 5 | | GD02215 | DC.. | 2 | | 001-099 |
| 0590 | 22 | | GA | | 2-3 | 31-41-21 | D00321C | | 5 | | GD02215 | DC.. | 2 | | 115-199 |
| 0591 | 22 | | GA | | 2-4 | 31-41-21 | D00321C | | 6 | | GD02214 | AC.. | 2 | | ALL |
| 0596 | 24 | | GK | | 3-0 | 34-46-12 | D00321B | J01 | | | D41451J | 17 | | *H | ALL |
| 0597 | 24 | | GK | | 3-7 | 34-46-12 | D00319B | J01 | | | D41451J | 17 | | *H | ALL |
| 0599 | 22 | | GA | | 2-8 | 77-31-11 | D04240C | | 3 | | GD02206 | AC.. | 2 | | 001-099 |
| 0599 | 20 | | GA | | 2-4 | 77-31-11 | D04240C | | 3 | | GD02204 | AC.. | 2 | | 115-199 |
| 0600 | 20 | | GA | | 2-4 | 77-31-11 | D04240C | | 4 | | GD02205 | ST.. | 2 | | 001-099 |
| 0600 | 20 | | GA | | 2-4 | 77-31-11 | D04240C | | 4 | | GD02204 | ST.. | 2 | | 115-199 |
| 0601 | 22 | | GA | | 2-5 | 77-31-11 | D40684J | | 4 | | D04240C | 2 | | | 001-099 |
| 0601 | 22 | | GA | | 2-4 | 77-31-11 | D40684J | | 4 | | D04240C | 2 | | | 115-199 |
| 0602 | 22 | | GA | | 2-9 | 77-31-11 | D41788J | | | FT | GD02205 | ST.. | 2 | | 001-099 |
| 0602 | 22 | | GA | | 2-8 | 77-31-11 | D41788J | | | FT | GD02215 | ST.. | 2 | | 115-199 |
| 0604 | 22 | | GA | | 2-9 | 77-31-11 | D41788J | | | FU | GD02205 | ST.. | 2 | | 001-099 |
| 0604 | 22 | | GA | | 2-8 | 77-31-11 | D41788J | | | FU | GD02215 | ST.. | 2 | | 115-199 |
| 0605 | 24 | | GK | | 3-5 | 75-31-11 | D00319B | J10 | | | D41772J | 2 | | *T | 001-099 |
| 0606 | 22 | | GA | | 3-1 | 77-31-11 | D41772J | | | FY | GD02206 | ST.. | 2 | | 001-099 |
| 0606 | 22 | | GA | | 3-3 | 77-31-11 | D41772J | | | FY | GD02204 | ST.. | 2 | | 115-199 |
| 0607 | 22 | | GA | | 3-1 | 77-31-11 | D41772J | | | FW | GD02206 | ST.. | 2 | | 001-099 |
| 0607 | 22 | | GA | | 3-3 | 77-31-11 | D41772J | | | FW | GD02204 | ST.. | 2 | | 115-199 |
| 0608 | 24 | | GK | | 2-8 | 33-51-11 | D00319E | A11 | | | D41058J | 16 | | *E | 001-099 |
| 0608 | 24 | | GK | | 2-9 | 33-51-11 | D00319E | A11 | | | D41058J | 16 | | *E | 115-199 |
| 0609 | 24 | | GK | | 4-0 | 33-51-11 | D00321E | A11 | | | D41058J | 16 | | *E | 001-099 |
| 0609 | 24 | | GK | | 4-1 | 33-51-11 | D00321E | A11 | | | D41058J | 16 | | *E | 115-199 |
| 0610 | 24 | | GK | | 3-11 | 32-61-12 | D00319D | E07 | | | D41867J | 34 | | *Y | 001-099 |
| 0610 | 24 | | GK | | 4-0 | 32-61-11 | D00319D | E07 | | | D41867J | 34 | | *Y | 115-199 |
| 0611 | 24 | | GK | | 5-3 | 32-61-12 | D00321D | E07 | | | D41867J | 34 | | *Y | 001-099 |
| 0611 | 24 | | GK | | 5-4 | 32-61-11 | D00321D | E07 | | | D41867J | 34 | | *Y | 115-199 |
| 0612 | 24 | | GK | | 3-9 | 32-61-12 | D00319E | J07 | | | D41867J | 35 | | *Y | 001-099 |
| 0612 | 24 | | GK | | 3-10 | 32-61-11 | D00319E | J07 | | | D41867J | 35 | | *Y | 115-199 |
| 0613 | 24 | | GK | | 5-2 | 32-61-12 | D00321E | J07 | | | D41867J | 35 | | *Y | 001-099 |
| 0613 | 24 | | GK | | 5-2 | 32-61-11 | D00321E | J07 | | | D41867J | 35 | | *Y | 115-199 |
| 0614 | 24 | | GK | | 3-10 | 32-61-12 | D00319B | F14 | | | D41867J | 36 | | *Y | 001-099 |
| 0614 | 24 | | GK | | 3-11 | 32-61-12 | D00319B | F14 | | | D41867J | 36 | | *Y | 115-199 |
| 0615 | 24 | | GK | | 5-3 | 32-61-12 | D00321B | F14 | | | D41867J | 36 | | *Y | ALL |
| 0616 | 24 | | GK | | 3-8 | 32-61-12 | D00319F | C02 | | | D41867J | 37 | | *Y | 001-099 |
| 0616 | 24 | | GK | | 3-9 | 32-61-12 | D00319F | C02 | | | D41867J | 37 | | *Y | 115-199 |
| 0617 | 24 | | GK | | 5-0 | 32-61-12 | D00321F | C02 | | | D41867J | 37 | | *Y | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 83

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | | | | | | | | | | | | | | | |
| | | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | |
| 0617 | 24 | GK | | | 5-1 | 32-61-12 | D00321F | C02 | | | D41867J | 37 | | *Y | 115-199 |
| 0618 | 24 | GK | | | 3-0 | 36-11-41 | D00319F | F01 | | | TB0207Y | A091 | BJ | | 001, 003-099 |
| 0618 | 24 | GK | | | 3-1 | 36-11-41 | D00319F | F01 | | | TB0207Y | A091 | BJ | | 002, 115-199 |
| 0619 | 24 | GK | | | 4-3 | 36-11-41 | D41844J | 4 | | | TB0207Y | A091 | BJ | | 001-099 |
| 0619 | 24 | GK | | | 4-0 | 36-11-41 | D41844J | 4 | | | TB0207Y | A091 | BJ | | 115-199 |
| 0620 | 24 | GK | | | 4-3 | 36-11-41 | D41844J | 5 | | | TB0207Y | A091 | BJ | | 001-099 |
| 0620 | 24 | GK | | | 4-0 | 36-11-41 | D41844J | 5 | | | TB0207Y | A091 | BJ | | 115-199 |
| 0621 | 24 | GK | | | 2-5 | 36-11-41 | D00321F | F01 | | | TB0207Y | A091 | BJ | | 001, 003-099 |
| 0621 | 24 | GK | | | 2-6 | 36-11-41 | D00321F | F01 | | | TB0207Y | A091 | BJ | | 002, 115-199 |
| 0622 | 22 | GA | | | 2-11 | 77-31-11 | D05602B | A15 | | | GD02205 | DC.. | 2 | | ALL |
| 0623 | 24 | GK | | | 4-10 | 75-31-11 | D00321B | J10 | | | D41772J | 2 | | *T | 001-099 |
| 0624 | 22 | GA | | | 3-11 | 77-31-11 | D05602C | 2 | | | D40704J | 9 | | | 001-099 |
| 0624 | 24 | GK | | | 3-11 | 77-31-11 | D05602C | 2 | | | D40704J | 9 | | | 115-199 |
| 0625 | 24 | GK | | | 2-9 | 21-58-21 | D00321A | K14 | | | D40584J | 8 | | *C | ALL |
| 0626 | 24 | GK | | | 3-11 | 21-58-21 | D00319A | K14 | | | D40584J | 8 | | *C | 001-099 |
| 0626 | 24 | GK | | | 4-0 | 21-58-21 | D00319A | K14 | | | D40584J | 8 | | *C | 115-199 |
| 0628 | 24 | GK | | | 3-8 | 21-58-21 | D00319A | G14 | | | D41844J | 9 | | *X | 001-099 |
| 0628 | 24 | GK | | | 3-5 | 21-58-21 | D00319A | G14 | | | D41844J | 9 | | *X | 115-199 |
| 0629 | 24 | GK | | | 5-1 | 21-58-21 | D00321A | G14 | | | D41844J | 9 | | *X | 001-099 |
| 0629 | 24 | GK | | | 4-10 | 21-58-21 | D00321A | G14 | | | D41844J | 9 | | *X | 115-199 |
| 0631 | 24 | GK | | | 2-10 | 21-58-13 | D00319A | D09 | | | D41058J | 35 | | *E | ALL |
| 0632 | 24 | GK | | | 4-3 | 21-58-13 | D00321A | D09 | | | D41058J | 35 | | *E | ALL |
| 0634 | 24 | GK | | | 3-11 | 21-58-13 | D00319A | E11 | | | D40584J | 44 | | *C | 001-099 |
| 0634 | 24 | GK | | | 4-0 | 21-58-13 | D00319A | E11 | | | D40584J | 44 | | *C | 115-199 |
| 0635 | 24 | GK | | | 2-9 | 21-58-13 | D00321A | E11 | | | D40584J | 44 | | *C | ALL |
| 0638 | 24 | GK | | | 3-4 | 21-58-12 | D00319F | F05 | | | D41844J | 7 | | *X | 001-099 |
| 0638 | 24 | GK | | | 3-2 | 21-58-12 | D00319F | F05 | | | D41844J | 7 | | *X | 115-199 |
| 0639 | 24 | GK | | | 4-9 | 21-58-12 | D00321F | F05 | | | D41844J | 7 | | *X | 001-099 |
| 0639 | 24 | GK | | | 4-6 | 21-58-12 | D00321F | F05 | | | D41844J | 7 | | *X | 115-199 |
| 0640 | 24 | GK | | | 3-7 | 21-58-12 | D00319D | E15 | | | D41844J | 8 | | *X | 001-099 |
| 0640 | 24 | GK | | | 3-5 | 21-58-12 | D00319D | E15 | | | D41844J | 8 | | *X | 115-199 |
| 0642 | 24 | GK | | | 5-0 | 21-58-12 | D00321D | E15 | | | D41844J | 8 | | *X | 001-099 |
| 0642 | 24 | GK | | | 4-9 | 21-58-12 | D00321D | E15 | | | D41844J | 8 | | *X | 115-199 |
| 0647 | 24 | GK | | | 3-0 | 26-11-11 | D00321E | A02 | | | D41738J | 2 | | *R | 001-099 |
| 0647 | 24 | GK | | | 3-1 | 26-11-11 | D00321E | A02 | | | D41738J | 2 | | *R | 115-199 |
| 0648 | 24 | GK | | | 2-10 | 26-11-11 | D00321B | E04 | | | D41738J | 4 | | *R | 001-099 |
| 0648 | 24 | GK | | | 2-11 | 26-11-11 | D00321B | E04 | | | D41738J | 4 | | *R | 115-199 |
| 0649 | 24 | GK | | | 3-0 | 26-11-11 | D00321E | G04 | | | D41738J | 3 | | *R | 001-099 |
| 0649 | 24 | GK | | | 3-1 | 26-11-11 | D00321E | G04 | | | D41738J | 3 | | *R | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 84

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | |
| 0657 | 24 | | GK | | 4-1 | 26-11-11 | D00319E | | G04 | | D41738J | | 3 | | *R | 001-099 | |
| 0657 | 24 | | GK | | 4-2 | 26-11-11 | D00319E | | G04 | | D41738J | | 3 | | *R | 115-199 | |
| 0658 | 24 | | GK | | 4-1 | 26-11-11 | D00319E | | A02 | | D41738J | | 2 | | *R | 001-099 | |
| 0658 | 24 | | GK | | 4-2 | 26-11-11 | D00319E | | A02 | | D41738J | | 2 | | *R | 115-199 | |
| 0659 | 24 | | GK | | 4-1 | 26-11-11 | D00319B | | E04 | | D41738J | | 4 | | *R | 001-099 | |
| 0659 | 24 | | GK | | 4-2 | 26-11-11 | D00319B | | E04 | | D41738J | | 4 | | *R | 115-199 | |
| 0661 | 24 | | GK | | 2-8 | 26-11-11 | D42023J | | 14 | | TB0207A | A087 | 2 | | | 001, 003-099 | |
| 0661 | 24 | | GK | | 2-9 | 26-11-11 | D42023J | | 14 | | TB0207A | A087 | 2 | | | 002 | |
| 0661 | 24 | | GK | | 2-10 | 26-11-11 | D42023J | | 14 | | TB0207A | A087 | 2 | | | 115-199 | |
| 0664 | 24 | | GK | | 4-1 | 26-11-12 | D00319B | | E06 | | D41738J | | 10 | | *R | 001-099 | |
| 0664 | 24 | | GK | | 2-10 | 26-11-12 | D00319B | | E06 | | D41734J | | 17 | | *P | 115-199 | |
| 0666 | 24 | | GK | | 2-10 | 26-11-12 | D00321B | | E06 | | D41738J | | 10 | | *R | 001-099 | |
| 0666 | 24 | | GK | | 3-3 | 26-11-12 | D00321B | | E06 | | D41734J | | 17 | | *P | 115-199 | |
| 0667 | 24 | | GK | | 2-11 | 26-11-12 | D00319A | | G04 | | D41734J | | 17 | | *P | 001-099 | |
| 0667 | 24 | | GK | | 4-3 | 26-11-12 | D00319A | | G04 | | D41738J | | 10 | | *R | 115-199 | |
| 0669 | 24 | | GK | | 3-4 | 26-11-12 | D00321A | | G04 | | D41734J | | 17 | | *P | 001-099 | |
| 0669 | 24 | | GK | | 3-0 | 26-11-12 | D00321A | | G04 | | D41738J | | 10 | | *R | 115-199 | |
| 0673 | 24 | | GK | | 3-7 | 26-11-21 | D00321A | | G02 | | D41736J | | 26 | | *Q | 001-099 | |
| 0673 | 24 | | GK | | 3-6 | 26-11-21 | D00321B | | E09 | | D41776J | | 2 | | *V | 115-199 | |
| 0674 | 24 | | GK | | 3-2 | 26-11-21 | D00319A | | G02 | | D41736J | | 26 | | *Q | 001-099 | |
| 0674 | 24 | | GK | | 3-1 | 26-11-21 | D00319B | | E09 | | D41776J | | 2 | | *V | 115-199 | |
| 0676 | 24 | | GK | | 3-6 | 26-11-21 | D00321B | | E09 | | D41776J | | 2 | | *V | 001-099 | |
| 0676 | 24 | | GK | | 3-7 | 26-11-21 | D00321A | | G02 | | D41736J | | 26 | | *Q | 115-199 | |
| 0677 | 24 | | GK | | 3-1 | 26-11-21 | D00319B | | E09 | | D41776J | | 2 | | *V | 001-099 | |
| 0677 | 24 | | GK | | 3-3 | 26-11-21 | D00319A | | G02 | | D41736J | | 26 | | *Q | 115-199 | |
| 0683 | 24 | | GK | | 3-6 | 26-11-21 | D00321D | | G03 | | D41736J | | 25 | | *Q | ALL | |
| 0684 | 24 | | GK | | 3-3 | 26-11-21 | D00319D | | G03 | | D41736J | | 25 | | *Q | 001-099 | |
| 0684 | 24 | | GK | | 3-2 | 26-11-21 | D00319D | | G03 | | D41736J | | 25 | | *Q | 115-199 | |
| 0689 | 24 | | GK | | 3-3 | 26-11-22 | D00319D | | G09 | | D41736J | | 55 | | *Q | 001-099 | |
| 0689 | 24 | | GK | | 3-2 | 26-11-22 | D00319D | | G09 | | D41736J | | 20 | | *Q | 115-199 | |
| 0690 | 24 | | GK | | 3-6 | 26-11-22 | D00321D | | G09 | | D41736J | | 55 | | *Q | 001-099 | |
| 0690 | 24 | | GK | | 3-6 | 26-11-22 | D00321D | | G09 | | D41736J | | 20 | | *Q | 115-199 | |
| 0691 | 24 | | GK | | 3-2 | 26-11-22 | D00319E | | G06 | | D41776J | | 5 | | *V | 001-099 | |
| 0691 | 24 | | GK | | 3-1 | 26-11-22 | D00319E | | G06 | | D41776J | | 5 | | *V | 115-199 | |
| 0693 | 24 | | GK | | 3-5 | 26-11-22 | D00321E | | G06 | | D41776J | | 5 | | *V | ALL | |
| 0697 | 24 | | GK | | 2-10 | 26-12-11 | D00321B | | G04 | | D41738J | | 13 | | *R | 001-099 | |
| 0697 | 24 | | GK | | 2-11 | 26-12-11 | D00321B | | G04 | | D41738J | | 13 | | *R | 115-199 | |
| 0699 | 24 | | GK | | 4-1 | 26-12-11 | D00319B | | G04 | | D41738J | | 13 | | *R | 001-099 | |
| 0699 | 24 | | GK | | 4-2 | 26-12-11 | D00319B | | G04 | | D41738J | | 13 | | *R | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 85

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0700 | 24 | | GK | | 2-11 | 26-12-11 | D00319A | G07 | | | D41734J | 19 | | *P | 001-099 |
| 0700 | 24 | | GK | | 3-0 | 26-12-11 | D00319A | G07 | | | D41734J | 19 | | *P | 115-199 |
| 0701 | 24 | | GK | | 3-4 | 26-12-11 | D00321A | G07 | | | D41734J | 19 | | *P | ALL |
| 0706 | 24 | | GK | | 3-5 | 26-12-21 | D00321E | G07 | | | D41776J | 7 | | *V | ALL |
| 0708 | 24 | | GK | | 3-2 | 26-12-21 | D00319E | G07 | | | D41776J | 7 | | *V | 001-099 |
| 0708 | 24 | | GK | | 3-1 | 26-12-21 | D00319E | G07 | | | D41776J | 7 | | *V | 115-199 |
| 0709 | 24 | | GK | | 3-6 | 26-12-21 | D00321D | G01 | | | D41736J | 22 | | *Q | ALL |
| 0710 | 24 | | GK | | 3-3 | 26-12-21 | D00319D | G01 | | | D41736J | 22 | | *Q | 001-099 |
| 0710 | 24 | | GK | | 3-2 | 26-12-21 | D00319D | G01 | | | D41736J | 22 | | *Q | 115-199 |
| 0716 | 24 | | GK | | 2-10 | 26-15-11 | D00321F | F02 | | | D41738J | 12 | | *R | 001-099 |
| 0716 | 24 | | GK | | 2-11 | 26-15-11 | D00321F | F02 | | | D41738J | 12 | | *R | 115-199 |
| 0718 | 24 | | GK | | 4-0 | 26-15-11 | D00319F | F02 | | | D41738J | 12 | | *R | ALL |
| 0719 | 24 | | GK | | 3-0 | 26-15-11 | D00321F | D04 | | | D41734J | 28 | | *P | ALL |
| 0721 | 24 | | GK | | 2-9 | 26-15-11 | D00319F | D04 | | | D41734J | 28 | | *P | 001-099 |
| 0721 | 24 | | GK | | 2-8 | 26-15-11 | D00319F | D04 | | | D41734J | 28 | | *P | 115-199 |
| 0722 | 24 | | GK | | 4-3 | 26-15-11 | D00319D | F04 | | | D41738J | 11 | | *R | ALL |
| 0724 | 24 | | GK | | 3-1 | 26-15-11 | D00321D | F04 | | | D41738J | 11 | | *R | 001-099 |
| 0724 | 24 | | GK | | 3-2 | 26-15-11 | D00321D | F04 | | | D41738J | 11 | | *R | 115-199 |
| 0729 | 24 | | GK | | 3-4 | 26-17-11 | D41734J | 26 | | | TB0207Y | C023 | BJ | | 001, 003-099, 115-199 |
| 0729 | 24 | | GK | | 3-5 | 26-17-11 | D41734J | 26 | | | TB0207Y | C023 | BJ | | 002 |
| 0730 | 24 | | GK | | 2-4 | 26-17-11 | D41451J | 37 | | | TB0207A | C087 | 2 | | 001, 003-099 |
| 0730 | 24 | | GK | | 2-5 | 26-17-11 | D41451J | 37 | | | TB0207A | C087 | 2 | | 002, 115-199 |
| 0731 | 24 | | GK | | 3-0 | 26-17-11 | D00319D | B10 | | | TB0207Y | C023 | BJ | | 001, 003-099 |
| 0731 | 24 | | GK | | 3-1 | 26-17-11 | D00319D | B10 | | | TB0207Y | C023 | BJ | | 002, 115-199 |
| 0732 | 24 | | GK | | 4-5 | 26-17-11 | D00321D | B10 | | | TB0207Y | C023 | BJ | | 001, 003-099, 115-199 |
| 0732 | 24 | | GK | | 4-6 | 26-17-11 | D00321D | B10 | | | TB0207Y | C023 | BJ | | 002 |
| 0733 | 24 | | GK | | 3-1 | 26-18-11 | D00321B | F04 | | | TB0207Y | A084 | BJ | | 001-099 |
| 0733 | 24 | | GK | | 3-2 | 26-18-11 | D00321B | F04 | | | TB0207Y | A084 | BJ | | 115-199 |
| 0734 | 24 | | GK | | 3-1 | 26-18-11 | D40584J | 21 | | | TB0207Y | A084 | BJ | | 001-099 |
| 0734 | 24 | | GK | | 3-3 | 26-18-11 | D40584J | 21 | | | TB0207Y | A084 | BJ | | 115-199 |
| 0735 | 24 | | GK | | 2-2 | 26-18-11 | D41734J | 29 | | | TB0207Y | A084 | BJ | | 001-099 |
| 0735 | 24 | | GK | | 2-3 | 26-18-11 | D41734J | 29 | | | TB0207Y | A084 | BJ | | 115-199 |
| 0736 | 24 | | GK | | 2-9 | 26-18-11 | D00319B | F04 | | | TB0207Y | A084 | BJ | | 001-099 |
| 0736 | 24 | | GK | | 2-11 | 26-18-11 | D00319B | F04 | | | TB0207Y | A084 | BJ | | 115-199 |
| 0740 | 24 | | GK | | 3-6 | 26-18-21 | D00321D | G04 | | | D41736J | 17 | | *Q | ALL |
| 0742 | 24 | | GK | | 3-3 | 26-18-21 | D00319D | G04 | | | D41736J | 17 | | *Q | 001-099 |
| 0742 | 24 | | GK | | 3-2 | 26-18-21 | D00319D | G04 | | | D41736J | 17 | | *Q | 115-199 |
| 0745 | 22 | | GA | | 3-3 | 26-21-11 | D41738J | 14 | | | TB0207Y | A085 | BJ | | 001-099 |
| 0745 | 22 | | GA | | 3-6 | 26-21-11 | D41738J | 14 | | | TB0207Y | A085 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 86

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0746 | 24 | | GK | | 2-11 | 26-21-11 | D00319D | | G02 | | TB0207Y | A085 | BJ | | 001-099 |
| 0746 | 24 | | GK | | 3-0 | 26-21-11 | D00319D | | G02 | | TB0207Y | A085 | BJ | | 115-199 |
| 0747 | 24 | | GK | | 3-1 | 26-21-11 | D00321D | | G02 | | TB0207Y | A085 | BJ | | 001-099 |
| 0747 | 24 | | GK | | 3-3 | 26-21-11 | D00321D | | G02 | | TB0207Y | A085 | BJ | | 115-199 |
| 0748 | 22 | | GA | | 3-3 | 26-21-11 | D41738J | | 15 | | TB0207Y | A085 | BJ | | 001-099 |
| 0748 | 22 | | GA | | 3-6 | 26-21-11 | D41738J | | 15 | | TB0207Y | A085 | BJ | | 115-199 |
| 0749 | 22 | | GA | | 2-5 | 26-21-11 | D41776J | | 10 | | TB0207Y | C085 | BJ | | 001-099 |
| 0749 | 22 | | GA | | 2-6 | 26-21-11 | D41776J | | 10 | | TB0207Y | C085 | BJ | | 115-199 |
| 0750 | 24 | | GK | | 2-8 | 26-21-11 | D00319F | | E03 | | TB0207Y | C085 | BJ | | 001-099 |
| 0750 | 24 | | GK | | 2-9 | 26-21-11 | D00319F | | E03 | | TB0207Y | C085 | BJ | | 115-199 |
| 0751 | 24 | | GK | | 2-10 | 26-21-11 | D00321F | | E03 | | TB0207Y | C085 | BJ | | 001-099 |
| 0751 | 24 | | GK | | 3-0 | 26-21-11 | D00321F | | E03 | | TB0207Y | C085 | BJ | | 115-199 |
| 0752 | 22 | | GA | | 2-5 | 26-21-11 | D41776J | | 8 | | TB0207Y | C085 | BJ | | 001-099 |
| 0752 | 22 | | GA | | 2-6 | 26-21-11 | D41776J | | 8 | | TB0207Y | C085 | BJ | | 115-199 |
| 0765 | 22 | | GA | | 2-10 | 77-31-11 | D05602C | | 3 | | GD02205 | AC.. | 2 | | 001-099 |
| 0765 | 20 | | GA | | 2-10 | 77-31-11 | D05602C | | 3 | | GD02205 | AC.. | 2 | | 115-199 |
| 0769 | 24 | | GK | | 3-3 | 26-22-21 | D00319D | | C09 | | D41776J | 36 | | *V | 001-099 |
| 0769 | 22 | | GA | | 3-2 | 26-22-21 | D41776J | | 36 | | TB0207Y | A042 | BJ | | 115-199 |
| 0770 | 24 | | GK | | 3-6 | 26-22-21 | D00321D | | C09 | | D41776J | 36 | | *V | 001-099 |
| 0770 | 24 | | GK | | 4-0 | 26-22-21 | D00321D | | C09 | | TB0207Y | A042 | BJ | | 115-199 |
| 0771 | 22 | | GA | | 4-3 | 26-22-21 | D41738J | | 43 | | TB0207Y | A042 | BJ | | 115-199 |
| 0772 | 24 | | GK | | 2-8 | 26-22-21 | D00319D | | C09 | | TB0207Y | A042 | BJ | | 115-199 |
| 0774 | 20 | | GA | | 2-10 | 77-31-11 | D05602C | | 4 | | GD02205 | ST.. | 2 | | ALL |
| 0777 | 22 | | GA | | 2-9 | 29-11-12 | D41058J | | 8 | | TB0207Y | C025 | BJ | | ALL |
| 0778 | 24 | | GK | | 4-6 | 29-11-12 | D00321A | | K11 | | TB0207Y | C025 | BJ | | 001, 003-099, 115-199 |
| 0778 | 24 | | GK | | 4-7 | 29-11-12 | D00321A | | K11 | | TB0207Y | C025 | BJ | | 002 |
| 0779 | 24 | | GK | | 3-1 | 29-11-12 | D00319A | | K11 | | TB0207Y | C025 | BJ | | 001, 003-099, 115-199 |
| 0779 | 24 | | GK | | 3-2 | 29-11-12 | D00319A | | K11 | | TB0207Y | C025 | BJ | | 002 |
| 0780 | 22 | | GA | | 2-9 | 29-11-12 | D41058J | | 27 | | TB0207Y | A027 | BJ | | 001-099 |
| 0780 | 22 | | GA | | 2-9 | 29-11-12 | D41058J | | 27 | | TB0207Z | 28 | BJ | | 115-199 |
| 0781 | 24 | | GK | | 4-5 | 29-11-12 | D00321D | | E14 | | TB0207Y | C026 | BJ | | 001, 003-099 |
| 0781 | 24 | | GK | | 4-6 | 29-11-12 | D00321D | | E14 | | TB0207Y | C026 | BJ | | 002 |
| 0781 | 24 | | GK | | 2-7 | 29-11-12 | D00321D | | E14 | | TB0207Z | 103 | BJ | | 115-199 |
| 0782 | 24 | | GK | | 3-1 | 29-11-12 | D00319D | | E14 | | TB0207Y | C026 | BJ | | 001-099 |
| 0782 | 24 | | GK | | 3-8 | 29-11-12 | D00319D | | E14 | | TB0207Z | 103 | BJ | | 115-199 |
| 0783 | 22 | | GA | | 3-11 | 29-11-12 | D41058J | | 26 | | TB0207Z | 103 | BJ | | 001-099 |
| 0783 | 22 | | GA | | 2-9 | 29-11-12 | D41058J | | 26 | | TB0207Z | 27 | BJ | | 115-199 |
| 0784 | 24 | | GK | | 2-7 | 29-11-12 | D00321A | | K02 | | TB0207Z | 103 | BJ | | 001-099 |
| 0784 | 24 | | GK | | 4-6 | 29-11-12 | D00321A | | K02 | | TB0207Z | 27 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 87

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-------------|----|----|------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0785 | 24 | | GK | 3-9 | 29-11-12 | D00319A | | K02 | | | TB0207Z | 103 | BJ | | 001-099 |
| 0785 | 24 | | GK | 3-1 | 29-11-12 | D00319A | | K02 | | | TB0207Z | 27 | BJ | | 115-199 |
| 0786 | 22 | | GA | 4-10 | 29-11-22 | D40584J | | 15 | | | TB0207Z | 13 | BJ | | 001, 003-099, 115-199 |
| 0786 | 22 | | GA | 4-11 | 29-11-22 | D40584J | | 15 | | | TB0207Z | 13 | BJ | | 002 |
| 0787 | 24 | | GK | 3-3 | 29-11-22 | D00319F | | K02 | | | TB0207Z | 13 | BJ | | 001, 003-099, 115-199 |
| 0787 | 24 | | GK | 3-4 | 29-11-22 | D00319F | | K02 | | | TB0207Z | 13 | BJ | | 002 |
| 0788 | 24 | | GK | 4-7 | 29-11-22 | D00321F | | K02 | | | TB0207Z | 13 | BJ | | 001, 003-099, 115-199 |
| 0788 | 24 | | GK | 4-8 | 29-11-22 | D00321F | | K02 | | | TB0207Z | 13 | BJ | | 002 |
| 0789 | 22 | | GA | 4-4 | 29-11-22 | D40584J | | 16 | | | TB0207Y | A024 | BJ | | 001, 003-099 |
| 0789 | 22 | | GA | 4-5 | 29-11-22 | D40584J | | 16 | | | TB0207Y | A024 | BJ | | 002, 115-199 |
| 0790 | 24 | | GK | 3-7 | 29-11-22 | D00319F | | C09 | | | TB0207Z | 104 | BJ | | 001-099 |
| 0790 | 24 | | GK | 3-5 | 29-11-22 | D00319F | | C09 | | | TB0207Z | 104 | BJ | | 115-199 |
| 0791 | 24 | | GK | 2-5 | 29-11-22 | D00321F | | C09 | | | TB0207Z | 104 | BJ | | 001-099 |
| 0791 | 24 | | GK | 2-4 | 29-11-22 | D00321F | | C09 | | | TB0207Z | 104 | BJ | | 115-199 |
| 0792 | 22 | | GA | 4-10 | 29-11-22 | D40584J | | 17 | | | TB0207Z | 14 | BJ | | 001, 003-099, 115-199 |
| 0792 | 22 | | GA | 4-11 | 29-11-22 | D40584J | | 17 | | | TB0207Z | 14 | BJ | | 002 |
| 0793 | 24 | | GK | 3-6 | 29-11-22 | D00319D | | K13 | | | TB0207Z | 14 | BJ | | 001, 003-099, 115-199 |
| 0793 | 24 | | GK | 3-7 | 29-11-22 | D00319D | | K13 | | | TB0207Z | 14 | BJ | | 002 |
| 0794 | 24 | | GK | 4-10 | 29-11-22 | D00321D | | K13 | | | TB0207Z | 14 | BJ | | 001, 003-099 |
| 0794 | 24 | | GK | 4-11 | 29-11-22 | D00321D | | K13 | | | TB0207Z | 14 | BJ | | 002 |
| 0794 | 24 | | GK | 4-9 | 29-11-22 | D00321D | | K13 | | | TB0207Z | 14 | BJ | | 115-199 |
| 0800 | 24 | | GK | 5-4 | 29-31-11 | D00321D | | K14 | | | D41794J | 4 | | *1 | 001-099 |
| 0800 | 24 | | GK | 6-0 | 29-31-11 | D00321D | | K14 | | | D41794J | 4 | | *1 | 115-199 |
| 0801 | 24 | | GK | 3-11 | 29-31-11 | D00319D | | K14 | | | D41794J | 4 | | *1 | 001-099 |
| 0801 | 24 | | GK | 4-2 | 29-31-11 | D00319D | | K14 | | | D41794J | 4 | | *1 | 115-199 |
| 0811 | 24 | | GK | 2-9 | 29-31-11 | D00319B | | H04 | | | D41698J | 16 | | *M | 001-099 |
| 0811 | 24 | | GK | 2-10 | 29-31-11 | D00319B | | H04 | | | D41698J | 16 | | *M | 115-199 |
| 0812 | 24 | | GK | 3-10 | 29-31-11 | D00321B | | H04 | | | D41698J | 16 | | *M | 001-099 |
| 0812 | 24 | | GK | 3-9 | 29-31-11 | D00321B | | H04 | | | D41698J | 16 | | *M | 115-199 |
| 0822 | 24 | | GK | 5-5 | 29-31-11 | D00321B | | H03 | | | D41792J | 1 | | *1 | 001-099 |
| 0822 | 24 | | GK | 6-1 | 29-31-11 | D00321B | | H03 | | | D41792J | 13 | | *1 | 115-199 |
| 0823 | 24 | | GK | 4-0 | 29-31-11 | D00319B | | H03 | | | D41792J | 1 | | *1 | 001-099 |
| 0823 | 24 | | GK | 4-2 | 29-31-11 | D00319B | | H03 | | | D41792J | 13 | | *1 | 115-199 |
| 0828 | 22 | | GA | 2-8 | 29-32-11 | D41058J | | 24 | | | TB0207Y | A029 | BJ | | 001, 003-099 |
| 0828 | 22 | | GA | 2-9 | 29-32-11 | D41058J | | 24 | | | TB0207Y | A029 | BJ | | 002, 115-199 |
| 0829 | 22 | | GA | 3-4 | 29-32-11 | D41734J | | 36 | | | TB0207Y | A029 | BJ | | 001, 003-099 |
| 0829 | 22 | | GA | 3-5 | 29-32-11 | D41734J | | 36 | | | TB0207Y | A029 | BJ | | 002 |
| 0829 | 22 | | GA | 3-4 | 29-32-11 | D41734J | | 5 | | | TB0207Y | A029 | BJ | | 115-199 |
| 0830 | 24 | | GK | 4-2 | 29-32-11 | D00321F | | G04 | | | TB0207Y | A029 | BJ | | 001, 003-099, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 88

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0830 | 24 | | GK | | 4-3 | 29-32-11 | D00321F | | G04 | | TB0207Y | A029 | BJ | | 002 |
| 0831 | 24 | | GK | | 2-9 | 29-32-11 | D00319F | | G04 | | TB0207Y | A029 | BJ | | 001, 003-099 |
| 0831 | 24 | | GK | | 2-10 | 29-32-11 | D00319F | | G04 | | TB0207Y | A029 | BJ | | 002, 115-199 |
| 0832 | 22 | | GA | | 2-8 | 29-32-11 | D41058J | | 25 | | TB0207Y | C029 | BJ | | 001, 003-099 |
| 0832 | 22 | | GA | | 2-9 | 29-32-11 | D41058J | | 25 | | TB0207Y | C029 | BJ | | 002, 115-199 |
| 0833 | 24 | | GK | | 4-4 | 29-32-11 | D00321B | | K07 | | TB0207Y | C029 | BJ | | 001, 003-099 |
| 0833 | 24 | | GK | | 4-5 | 29-32-11 | D00321B | | K07 | | TB0207Y | C029 | BJ | | 002, 115-199 |
| 0834 | 22 | | GA | | 2-11 | 29-32-11 | D41867J | | 22 | | TB0207Y | C029 | BJ | | 001, 003-099 |
| 0834 | 22 | | GA | | 3-0 | 29-32-11 | D41867J | | 22 | | TB0207Y | C029 | BJ | | 002 |
| 0834 | 22 | | GA | | 3-1 | 29-32-11 | D41867J | | 22 | | TB0207Y | C029 | BJ | | 115-199 |
| 0835 | 24 | | GK | | 2-11 | 29-32-11 | D00319B | | K07 | | TB0207Y | C029 | BJ | | 001, 003-099 |
| 0835 | 24 | | GK | | 3-1 | 29-32-11 | D00319B | | K07 | | TB0207Y | C029 | BJ | | 002 |
| 0835 | 24 | | GK | | 3-0 | 29-32-11 | D00319B | | K07 | | TB0207Y | C029 | BJ | | 115-199 |
| 0836 | 22 | | GA | | 4-4 | 29-32-21 | D40584J | | 1 | | TB0207Y | A031 | BJ | | 001, 003-099 |
| 0836 | 22 | | GA | | 4-5 | 29-32-21 | D40584J | | 1 | | TB0207Y | A031 | BJ | | 002, 115-199 |
| 0837 | 22 | | GA | | 3-7 | 29-32-21 | D41736J | | 27 | | TB0207Y | A031 | BJ | | 001, 003-099, 115-199 |
| 0837 | 22 | | GA | | 3-8 | 29-32-21 | D41736J | | 27 | | TB0207Y | A031 | BJ | | 002 |
| 0838 | 24 | | GK | | 4-6 | 29-32-21 | D00321A | | K04 | | TB0207Y | A031 | BJ | | 001, 003-099, 115-199 |
| 0838 | 24 | | GK | | 4-7 | 29-32-21 | D00321A | | K04 | | TB0207Y | A031 | BJ | | 002 |
| 0839 | 24 | | GK | | 3-1 | 29-32-21 | D00319A | | K04 | | TB0207Y | A031 | BJ | | 001, 003-099, 115-199 |
| 0839 | 24 | | GK | | 3-2 | 29-32-21 | D00319A | | K04 | | TB0207Y | A031 | BJ | | 002 |
| 0840 | 22 | | GA | | 4-4 | 29-32-21 | D40584J | | 2 | | TB0207Y | C031 | BJ | | 001, 003-099 |
| 0840 | 22 | | GA | | 4-5 | 29-32-21 | D40584J | | 2 | | TB0207Y | C031 | BJ | | 002, 115-199 |
| 0841 | 24 | | GK | | 4-6 | 29-32-21 | D00321A | | K08 | | TB0207Y | C031 | BJ | | 001, 003-099, 115-199 |
| 0841 | 24 | | GK | | 4-7 | 29-32-21 | D00321A | | K08 | | TB0207Y | C031 | BJ | | 002 |
| 0842 | 22 | | GA | | 2-7 | 29-32-21 | D42086J | | 29 | | TB0207Y | C031 | BJ | | 001, 003-099 |
| 0842 | 22 | | GA | | 2-8 | 29-32-21 | D42086J | | 29 | | TB0207Y | C031 | BJ | | 002 |
| 0842 | 22 | | GA | | 2-5 | 29-32-21 | D42086J | | 29 | | TB0207Y | C031 | BJ | | 115-199 |
| 0843 | 24 | | GK | | 3-1 | 29-32-21 | D00319A | | K08 | | TB0207Y | C031 | BJ | | 001, 003-099, 115-199 |
| 0843 | 24 | | GK | | 3-2 | 29-32-21 | D00319A | | K08 | | TB0207Y | C031 | BJ | | 002 |
| 0845 | 24 | | GK | | 3-4 | 29-33-11 | D00321A | | F04 | | D41734J | 30 | | *P | ALL |
| 0846 | 24 | | GK | | 2-11 | 29-33-11 | D00319A | | F04 | | D41734J | 30 | | *P | 001-099 |
| 0846 | 24 | | GK | | 3-0 | 29-33-11 | D00319A | | F04 | | D41734J | 30 | | *P | 115-199 |
| 0851 | 24 | | GK | | 3-4 | 29-33-11 | D00321A | | F03 | | D41734J | 31 | | *P | ALL |
| 0852 | 24 | | GK | | 2-11 | 29-33-11 | D00319A | | F03 | | D41734J | 31 | | *P | 001-099 |
| 0852 | 24 | | GK | | 3-0 | 29-33-11 | D00319A | | F03 | | D41734J | 31 | | *P | 115-199 |
| 0854 | 24 | | GK | | 3-4 | 29-33-11 | D00321E | | A03 | | TB0207Y | C063 | BJ | | 001, 003-099 |
| 0854 | 24 | | GK | | 3-5 | 29-33-11 | D00321E | | A03 | | TB0207Y | C063 | BJ | | 002, 115-199 |
| 0855 | 24 | | GK | | 2-6 | 29-33-11 | D00319E | | A03 | | TB0207Y | C063 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 89

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | | | | | | | | | | | | | | | |
| | | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | |
| 0857 | 24 | GK | | | 3-5 | 29-33-11 | D00321D | | B06 | | TB0207Y | C065 | BJ | | 001, 003-099 |
| 0857 | 24 | GK | | | 3-6 | 29-33-11 | D00321D | | B06 | | TB0207Y | C065 | BJ | | 002 |
| 0857 | 24 | GK | | | 3-7 | 29-33-11 | D00321D | | B06 | | TB0207Y | C065 | BJ | | 115-199 |
| 0858 | 24 | GK | | | 2-7 | 29-33-11 | D00319D | | B06 | | TB0207Y | C065 | BJ | | 001-099 |
| 0858 | 24 | GK | | | 2-8 | 29-33-11 | D00319D | | B06 | | TB0207Y | C065 | BJ | | 115-199 |
| 0860 | 24 | GK | | | 3-4 | 29-33-11 | D00321A | | F05 | | D41734J | 32 | | *P | ALL |
| 0861 | 24 | GK | | | 2-11 | 29-33-11 | D00319A | | F05 | | D41734J | 32 | | *P | 001-099 |
| 0861 | 24 | GK | | | 3-0 | 29-33-11 | D00319A | | F05 | | D41734J | 32 | | *P | 115-199 |
| 0863 | 24 | GK | | | 3-4 | 29-33-11 | D00321E | | C07 | | TB0207Y | C064 | BJ | | 001, 003-099 |
| 0863 | 24 | GK | | | 3-5 | 29-33-11 | D00321E | | C07 | | TB0207Y | C064 | BJ | | 002, 115-199 |
| 0864 | 24 | GK | | | 2-6 | 29-33-11 | D00319E | | C07 | | TB0207Y | C064 | BJ | | ALL |
| 0866 | 24 | GK | | | 3-6 | 29-35-11 | D00321D | | K07 | | TB0207Y | C056 | BJ | | 001, 003-099 |
| 0866 | 24 | GK | | | 3-7 | 29-35-11 | D00321D | | K07 | | TB0207Y | C056 | BJ | | 002 |
| 0866 | 24 | GK | | | 3-8 | 29-35-11 | D00321D | | K07 | | TB0207Y | C056 | BJ | | 115-199 |
| 0867 | 24 | GK | | | 2-5 | 29-35-11 | D00319D | | K07 | | TB0207Y | C056 | BJ | | 001, 003-099 |
| 0867 | 24 | GK | | | 2-6 | 29-35-11 | D00319D | | K07 | | TB0207Y | C056 | BJ | | 002 |
| 0867 | 24 | GK | | | 2-7 | 29-35-11 | D00319D | | K07 | | TB0207Y | C056 | BJ | | 115-199 |
| 0869 | 24 | GK | | | 5-2 | 29-35-11 | D00321F | | C10 | | D41792J | 4 | | *1 | 001-099 |
| 0869 | 24 | GK | | | 5-4 | 29-35-11 | D00321F | | C10 | | D41792J | 4 | | *1 | 115-199 |
| 0870 | 24 | GK | | | 3-10 | 29-35-11 | D00319F | | C10 | | D41792J | 4 | | *1 | 001-099 |
| 0870 | 24 | GK | | | 4-1 | 29-35-11 | D00319F | | C10 | | D41792J | 4 | | *1 | 115-199 |
| 0872 | 24 | GK | | | 3-7 | 29-35-11 | D00321A | | H02 | | TB0207Y | A056 | BJ | | 001, 003-099 |
| 0872 | 24 | GK | | | 3-8 | 29-35-11 | D00321A | | H02 | | TB0207Y | A056 | BJ | | 002 |
| 0872 | 24 | GK | | | 3-9 | 29-35-11 | D00321A | | H02 | | TB0207Y | A056 | BJ | | 115-199 |
| 0873 | 24 | GK | | | 2-4 | 29-35-11 | D00319A | | H02 | | TB0207Y | A056 | BJ | | 001, 003-099 |
| 0873 | 24 | GK | | | 2-5 | 29-35-11 | D00319A | | H02 | | TB0207Y | A056 | BJ | | 002 |
| 0873 | 24 | GK | | | 2-7 | 29-35-11 | D00319A | | H02 | | TB0207Y | A056 | BJ | | 115-199 |
| 0876 | 24 | GK | | | 3-1 | 31-41-19 | D41065J | | 2 | | TB0207Y | A055 | BJ | | 001, 003-099 |
| 0876 | 24 | GK | | | 3-2 | 31-41-19 | D41065J | | 2 | | TB0207Y | A055 | BJ | | 002, 115-199 |
| 0877 | 24 | GK | | | 3-2 | 28-22-21 | D00319E | | C01 | | D41776J | 4 | | *V | 001-099 |
| 0877 | 24 | GK | | | 3-1 | 28-22-21 | D00319E | | C01 | | D41776J | 4 | | *V | 115-199 |
| 0878 | 24 | GK | | | 3-5 | 28-22-21 | D00321E | | C01 | | D41776J | 4 | | *V | ALL |
| 0880 | 24 | GK | | | 3-0 | 28-22-21 | D00321E | | D05 | | D41738J | 9 | | *R | 001-099 |
| 0880 | 24 | GK | | | 3-1 | 28-22-21 | D00321E | | D05 | | D41738J | 9 | | *R | 115-199 |
| 0881 | 24 | GK | | | 4-1 | 28-22-21 | D00319E | | D05 | | D41738J | 9 | | *R | 001-099 |
| 0881 | 24 | GK | | | 4-2 | 28-22-21 | D00319E | | D05 | | D41738J | 9 | | *R | 115-199 |
| 0883 | 24 | GK | | | 2-6 | 28-41-11 | D00319E | | D04 | | D41628J | 2 | | *J | ALL |
| 0884 | 24 | GK | | | 2-11 | 31-41-19 | D41879J | | 5 | | D41065J | 14 | | | 001-099 |
| 0884 | 24 | GK | | | 2-9 | 31-41-19 | D41879J | | 5 | | D41065J | 14 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 90

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 0885 | 24 | | GK | | 3-5 | 28-41-11 | D00321E | | D04 | | D41628J | 2 | | *J | ALL |
| 0887 | 24 | | GK | | 2-6 | 28-41-13 | D00319E | | D13 | | D41628J | 1 | | *J | ALL |
| 0888 | 24 | | GK | | 3-5 | 28-41-13 | D00321E | | D13 | | D41628J | 1 | | *J | ALL |
| 0892 | 24 | | GK | | 4-11 | 28-22-31 | D00321E | | C02 | | D41844J | 10 | | *X | 001-008 |
| 0892 | 24 | | GK | | 5-1 | 28-22-31 | D00321A | | K05 | | D41844J | 10 | | *X | 009-099 |
| 0892 | 24 | | GK | | 4-8 | 28-22-31 | D00321E | | C02 | | D41844J | 10 | | *X | 115-199 |
| 0893 | 24 | | GK | | 3-6 | 28-22-31 | D00319E | | C02 | | D41844J | 10 | | *X | 001-008 |
| 0893 | 24 | | GK | | 3-8 | 28-22-31 | D00319A | | K05 | | D41844J | 10 | | *X | 009-099 |
| 0893 | 24 | | GK | | 3-4 | 28-22-31 | D00319E | | C02 | | D41844J | 10 | | *X | 115-199 |
| 0895 | 24 | | GK | | 2-9 | 28-42-21 | D00319F | | D10 | | D41734J | 44 | | *P | 001-099 |
| 0895 | 24 | | GK | | 2-8 | 28-42-21 | D00319F | | D10 | | D41734J | 44 | | *P | 115-199 |
| 0896 | 24 | | GK | | 3-0 | 28-42-21 | D00321F | | D10 | | D41734J | 44 | | *P | ALL |
| 0913 | 24 | | GK | | 2-10 | 32-46-11 | D41664J | | 20 | | TB0207Y | A083 | BJ | | 115-199 |
| 0914 | 24 | | GK | | 3-1 | 32-46-11 | D00321E | | J15 | | TB0207Y | A083 | BJ | | 115-199 |
| 0915 | 24 | | GK | | 2-11 | 32-46-11 | D00319E | | J15 | | TB0207Y | A083 | BJ | | 115-199 |
| 0916 | 24 | | GK | | 4-1 | 73-21-12 | D00319B | | G10 | | D41738J | 25 | | *R | 001-099 |
| 0916 | 24 | | GK | | 4-2 | 73-21-12 | D00319B | | G10 | | D41738J | 25 | | *R | 115-199 |
| 0917 | 24 | | GK | | 2-10 | 73-21-12 | D00321B | | G10 | | D41738J | 25 | | *R | 001-099 |
| 0917 | 24 | | GK | | 2-11 | 73-21-12 | D00321B | | G10 | | D41738J | 25 | | *R | 115-199 |
| 0918 | 24 | | GK | | 4-2 | 73-21-12 | D41879J | | 49 | | D41738J | 32 | | | 001-099 |
| 0918 | 24 | | GK | | 4-4 | 73-21-12 | D41738J | | 32 | | D41879J | 49 | | | 115-199 |
| 0921 | 22 | | GA | | 3-4 | 28-42-11 | D41058J | | 12 | | TB0207Y | C095 | BJ | | 001, 003-099 |
| 0921 | 22 | | GA | | 3-5 | 28-42-11 | D41058J | | 12 | | TB0207Y | C095 | BJ | | 002 |
| 0921 | 22 | | GA | | 3-6 | 28-42-11 | D41058J | | 12 | | TB0207Y | C094 | BJ | | 115-199 |
| 0922 | 24 | | GK | | 2-5 | 28-42-11 | D00321F | | H09 | | TB0207Y | C095 | BJ | | 001, 003-099 |
| 0922 | 24 | | GK | | 2-6 | 28-42-11 | D00321F | | H09 | | TB0207Y | C095 | BJ | | 002 |
| 0922 | 24 | | GK | | 2-6 | 28-42-11 | D00321F | | H09 | | TB0207Y | C094 | BJ | | 115-199 |
| 0923 | 22 | | GA | | 2-9 | 28-42-11 | D41776J | | 1 | | TB0207Y | C095 | BJ | | 001-099 |
| 0923 | 22 | | GA | | 2-10 | 28-42-11 | D41776J | | 1 | | TB0207Y | C094 | BJ | | 115-199 |
| 0924 | 24 | | GK | | 3-0 | 28-42-11 | D00319F | | H09 | | TB0207Y | C095 | BJ | | 001, 003-099 |
| 0924 | 24 | | GK | | 3-1 | 28-42-11 | D00319F | | H09 | | TB0207Y | C095 | BJ | | 002 |
| 0924 | 24 | | GK | | 3-1 | 28-42-11 | D00319F | | H09 | | TB0207Y | C094 | BJ | | 115-199 |
| 0925 | 22 | | GA | | 2-8 | 28-42-11 | D40584J | | 40 | | TB0207Y | A097 | BJ | | 001-099 |
| 0925 | 22 | | GA | | 2-9 | 28-42-11 | D40584J | | 40 | | TB0207Y | A097 | BJ | | 115-199 |
| 0926 | 24 | | GK | | 2-9 | 28-42-11 | D00321D | | H03 | | TB0207Y | A097 | BJ | | ALL |
| 0927 | 22 | | GA | | 2-8 | 28-42-11 | D41720J | | 2 | | TB0207Y | A097 | BJ | | ALL |
| 0928 | 24 | | GK | | 3-4 | 28-42-11 | D00319D | | H03 | | TB0207Y | A097 | BJ | | ALL |
| 0930 | 24 | | GK | | 2-10 | 28-42-11 | D00321D | | H06 | | D40584J | 29 | | *C | 001-099 |
| 0930 | 24 | | GK | | 2-11 | 28-42-11 | D00321D | | H06 | | D40584J | 29 | | *C | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 91

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | |
| 0931 | 24 | GK | | | 4-0 | 28-42-11 | D00319D | H06 | | | D40584J | 29 | | *C | ALL |
| 0932 | 22 | GA | | | 3-11 | 28-42-11 | D40584J | 19 | | | TB0207Y | A046 | BJ | | 001-099 |
| 0932 | 22 | GA | | | 4-0 | 28-42-11 | D40584J | 19 | | | TB0207Y | A046 | BJ | | 115-199 |
| 0934 | 24 | GK | | | 3-11 | 28-42-11 | D00321F | J09 | | | D41058J | 14 | | *E | ALL |
| 0935 | 24 | GK | | | 2-6 | 28-42-11 | D00319F | J09 | | | D41058J | 14 | | *E | 001-099 |
| 0935 | 24 | GK | | | 2-7 | 28-42-11 | D00319F | J09 | | | D41058J | 14 | | *E | 115-199 |
| 0936 | 22 | GA | | | 2-4 | 28-42-11 | D41058J | 13 | | | TB0207Y | A045 | BJ | | 001-099 |
| 0936 | 22 | GA | | | 2-3 | 28-42-11 | D41058J | 13 | | | TB0207Y | A045 | BJ | | 115-199 |
| 0937 | 22 | GA | | | 2-8 | 28-42-11 | D40584J | 20 | | | TB0207Y | C097 | BJ | | 001-099 |
| 0937 | 22 | GA | | | 2-9 | 28-42-11 | D40584J | 20 | | | TB0207Y | C097 | BJ | | 115-199 |
| 0938 | 24 | GK | | | 2-9 | 28-42-11 | D00321D | H08 | | | TB0207Y | C097 | BJ | | ALL |
| 0939 | 22 | GA | | | 2-11 | 28-42-11 | D41738J | 1 | | | TB0207Y | C097 | BJ | | 001-099 |
| 0939 | 22 | GA | | | 3-0 | 28-42-11 | D41738J | 1 | | | TB0207Y | C097 | BJ | | 115-199 |
| 0940 | 24 | GK | | | 3-4 | 28-42-11 | D00319D | H08 | | | TB0207Y | C097 | BJ | | ALL |
| 0941 | 22 | GA | | | 3-5 | 28-42-11 | D41058J | 15 | | | TB0207Y | C098 | BJ | | 001-099 |
| 0941 | 22 | GA | | | 3-6 | 28-42-11 | D41058J | 15 | | | TB0207Y | C098 | BJ | | 115-199 |
| 0942 | 24 | GK | | | 2-6 | 28-42-11 | D00321F | H08 | | | TB0207Y | C098 | BJ | | ALL |
| 0943 | 22 | GA | | | 3-1 | 28-42-11 | D41698J | 9 | | | TB0207Y | C098 | BJ | | ALL |
| 0944 | 24 | GK | | | 3-1 | 28-42-11 | D00319F | H08 | | | TB0207Y | C098 | BJ | | ALL |
| 0946 | 24 | GK | | | 3-10 | 32-42-11 | D00321B | F15 | | | D41664J | 9 | | *L | 001-099 |
| 0946 | 24 | GK | | | 3-9 | 32-42-11 | D00321B | F15 | | | D41664J | 38 | | *L | 115-199 |
| 0948 | 24 | GK | | | 2-9 | 32-42-11 | D00319B | F15 | | | D41664J | 9 | | *L | 001-099 |
| 0948 | 24 | GK | | | 2-10 | 32-42-11 | D00319B | F15 | | | D41664J | 38 | | *L | 115-199 |
| 0951 | 24 | GK | | | 3-9 | 32-42-11 | D00319D | B12 | | | D41451J | 32 | | *H | 001-099 |
| 0951 | 24 | GK | | | 2-11 | 32-42-11 | D00319D | B12 | | | D41664J | 40 | | *L | 115-199 |
| 0952 | 24 | GK | | | 3-0 | 32-42-11 | D00321D | B12 | | | D41451J | 32 | | *H | 001-099 |
| 0952 | 24 | GK | | | 3-10 | 32-42-11 | D00321D | B12 | | | D41664J | 40 | | *L | 115-199 |
| 0954 | 24 | GK | | | 2-8 | 32-42-11 | D00319F | H10 | | | D41664J | 11 | | *L | 001-099 |
| 0954 | 24 | GK | | | 2-8 | 32-42-11 | D00319F | H10 | | | D41664J | 41 | | *L | 115-199 |
| 0955 | 24 | GK | | | 3-7 | 32-42-11 | D00321F | H10 | | | D41664J | 11 | | *L | 001-099 |
| 0955 | 24 | GK | | | 3-7 | 32-42-11 | D00321F | H10 | | | D41664J | 41 | | *L | 115-199 |
| 0956 | 24 | GK | | | 3-1 | 32-44-11 | D00319A | G03 | | | TB0207Y | C027 | BJ | | 001, 003-099 |
| 0956 | 24 | GK | | | 3-2 | 32-44-11 | D00319A | G03 | | | TB0207Y | C027 | BJ | | 002 |
| 0956 | 24 | GK | | | 3-0 | 32-44-11 | D00319A | G03 | | | D41734J | 52 | | *P | 115-199 |
| 0957 | 24 | GK | | | 4-6 | 32-44-11 | D00321A | G03 | | | TB0207Y | C027 | BJ | | 001, 003-099 |
| 0957 | 24 | GK | | | 4-7 | 32-44-11 | D00321A | G03 | | | TB0207Y | C027 | BJ | | 002 |
| 0957 | 24 | GK | | | 3-4 | 32-44-11 | D00321A | G03 | | | D41734J | 52 | | *P | 115-199 |
| 0961 | 24 | GK | | | 3-6 | 75-31-11 | D00319D | J03 | | | D41788J | 3 | | *1 | 001-099 |
| 0964 | 24 | GK | | | 3-1 | 27-62-11 | D00319A | G09 | | | D41720J | 5 | | *N | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 92

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | |
| 0965 | 24 | | GK | | 3-6 | 27-62-11 | D00321A | G09 | | | D41720J | 5 | | *N | ALL | |
| 0967 | 24 | | GK | | 3-4 | 27-18-11 | D00321E | H05 | | | TB0207Y | A067 | BJ | | 001, 003-099 | |
| 0967 | 24 | | GK | | 3-5 | 27-18-11 | D00321E | H05 | | | TB0207Y | A067 | BJ | | 002, 115-199 | |
| 0968 | 24 | | GK | | 2-5 | 27-18-11 | D00319E | H05 | | | TB0207Y | A067 | BJ | | 001, 003-099 | |
| 0968 | 24 | | GK | | 2-6 | 27-18-11 | D00319E | H05 | | | TB0207Y | A067 | BJ | | 002, 115-199 | |
| 0973 | 24 | | GK | | 3-6 | 27-18-11 | D00321E | H04 | | | TB0207Y | A058 | BJ | | 001-099 | |
| 0973 | 24 | | GK | | 3-7 | 27-18-11 | D00321E | H04 | | | TB0207Y | A058 | BJ | | 115-199 | |
| 0974 | 24 | | GK | | 2-4 | 27-18-11 | D00319E | H04 | | | TB0207Y | A058 | BJ | | 001-099 | |
| 0974 | 24 | | GK | | 2-5 | 27-18-11 | D00319E | H04 | | | TB0207Y | A058 | BJ | | 115-199 | |
| 0978 | 24 | | GK | | 3-4 | 27-28-11 | D41628J | 23 | | | D40684J | 2 | | | 001-099 | |
| 0978 | 22 | | GA | | 3-3 | 27-28-11 | D41628J | 23 | | | D40684J | 2 | | | 115-199 | |
| 0979 | 24 | | GK | | 2-2 | 27-28-11 | D41628J | 17 | | | GD02208 | ST.. | 2 | | 001-099 | |
| 0979 | 24 | | GK | | 2-4 | 27-28-11 | D41628J | 17 | | | GD02208 | ST.. | 2 | | 115-199 | |
| 0980 | 24 | | GK | | 2-4 | 27-28-11 | D00319E | H10 | | | TB0207Y | C055 | BJ | | 001-099 | |
| 0980 | 24 | | GK | | 2-5 | 27-28-11 | D00319E | H10 | | | TB0207Y | C055 | BJ | | 115-199 | |
| 0981 | 24 | | GK | | 3-5 | 27-28-11 | D00321E | H10 | | | TB0207Y | C055 | BJ | | 001, 003-099 | |
| 0981 | 24 | | GK | | 3-6 | 27-28-11 | D00321E | H10 | | | TB0207Y | C055 | BJ | | 002 | |
| 0981 | 24 | | GK | | 3-7 | 27-28-11 | D00321E | H10 | | | TB0207Y | C055 | BJ | | 115-199 | |
| 0985 | 22 | | GA | | 1-11 | 27-38-11 | D40704J | 1 | | | D41632J | 14 | | | 001-099 | |
| 0985 | 22 | | GA | | 1-10 | 27-38-11 | D40704J | 1 | | | D41632J | 14 | | | 115-199 | |
| 0986 | 24 | | GK | | 2-9 | 27-38-11 | D41632J | 5 | | | GD02208 | ST.. | 2 | | 001-099 | |
| 0986 | 24 | | GK | | 2-10 | 27-38-11 | D41632J | 5 | | | GD02208 | ST.. | 2 | | 115-199 | |
| 0987 | 24 | | GK | | 2-2 | 27-38-11 | D41628J | 47 | | | GD02208 | ST.. | 2 | | 001-099 | |
| 0987 | 24 | | GK | | 2-4 | 27-38-11 | D41628J | 47 | | | GD02208 | ST.. | 2 | | 115-199 | |
| 0989 | 22 | | GA | | 3-4 | 27-38-11 | D40684J | 11 | | | D41628J | 18 | | | 001-099 | |
| 0989 | 22 | | GA | | 3-3 | 27-38-11 | D40684J | 11 | | | D41628J | 18 | | | 115-199 | |
| 0991 | 24 | | GK | | 3-8 | 34-45-02 | D00319A | REF | VM | | D41451J | 4 | | *H | 001-002 | |
| 0991 | 24 | | GK | | 3-8 | 34-45-02 | D00319E | G03 | | | D41451J | 4 | | *H | 003-099 | |
| 0991 | 24 | | GK | | 3-9 | 34-45-02 | D00319A | REF | VP | | D41451J | 4 | | *H | 115-199 | |
| 0992 | 24 | | GK | | 3-1 | 34-45-02 | D00321A | REF | VM | | D41451J | 4 | | *H | 001-002 | |
| 0992 | 24 | | GK | | 2-11 | 34-45-02 | D00321E | G03 | | | D41451J | 4 | | *H | 003-099 | |
| 0992 | 24 | | GK | | 3-1 | 34-45-02 | D00321A | REF | VP | | D41451J | 4 | | *H | 115-199 | |
| 0997 | 24 | | GK | | 3-6 | 27-38-11 | D00321E | H07 | | | TB0207Y | A059 | BJ | | 001-099 | |
| 0997 | 24 | | GK | | 3-7 | 27-38-11 | D00321E | H07 | | | TB0207Y | A059 | BJ | | 115-199 | |
| 0998 | 24 | | GK | | 2-4 | 27-38-11 | D00319E | H07 | | | TB0207Y | A059 | BJ | | 001-099 | |
| 0998 | 24 | | GK | | 2-5 | 27-38-11 | D00319E | H07 | | | TB0207Y | A059 | BJ | | 115-199 | |
| 1004 | 24 | | GK | | 3-11 | 28-22-32 | D00321F | F03 | | | D41058J | 46 | | *E | 009-099 | |
| 1005 | 24 | | GK | | 2-6 | 28-22-32 | D00319F | F03 | | | D41058J | 46 | | *E | 009-099 | |
| 1006 | 24 | | GK | | 3-11 | 28-22-32 | D00321F | H04 | | | D41058J | 47 | | *E | 009-099 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 93

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|-------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 1007 | 24 | | GK | | 2-6 | 28-22-32 | D00319F | H04 | | | D41058J | 47 | | *E | 009-099 |
| 1156 | 22 | | GA | | 5-0 | 34-12-62 | SM00308 | | WI | | D42093J | 8 | | | ALL |
| 1172 | 22 | | GA | | 3-0 | 34-12-62 | D00319B | G11 | | | SM00308 | | WI | | ALL |
| 1173 | 22 | | GA | | 4-0 | 34-12-62 | D00321B | G11 | | | SM00308 | | WI | | ALL |
| 1537 | 22 | | GT | AA | 3-1 | 27-18-11 | D41720J | | 13 | | R10151 | A | \$ | | 001-099 |
| 1537 | 22 | | GT | AA | 3-0 | 27-18-11 | D41720J | | 13 | | R10151 | A | \$ | | 115-199 |
| 1537Z | | | | AA | 0-0 | 27-18-11 | D41720J | DED | | | R10151 | = GND | F | | ALL |
| 1557 | 22 | | GT | AC | 2-7 | 27-18-11 | D41698J | | 6 | | R10152 | A | \$ | | 001-099 |
| 1557 | 22 | | GT | AC | 2-6 | 27-18-11 | D41698J | | 6 | | R10152 | A | \$ | | 115-199 |
| 1557Z | | | | AC | 0-0 | 27-18-11 | D41698J | DED | | | R10152 | = GND | F | | ALL |
| 1560 | 22 | | GT | JD | 3-1 | 31-41-11 | D00319C | | 1 | | D40684J | 5 | | | 115-199 |
| 1560Z | | | | JD | 0-0 | 31-41-11 | D00319C | DED | | | D40684J | DED | | | 115-199 |
| 1588 | 22 | | GT | JE | 3-1 | 31-41-21 | D00321C | | 1 | | D40704J | 3 | | | 115-199 |
| 1588Z | | | | JE | 0-0 | 31-41-21 | D00321C | DED | | | D40704J | DED | | | 115-199 |
| 2002B | 24 | | GL | AB | 3-10 | 49-71-11 | D41660J | | 17 | | TB0207C | A122 | 2 | | 115-199 |
| 2002R | 24 | | GL | AB | 0-0 | 49-71-11 | D41660J | | 18 | | TB0207C | CAP | Y | | 115-199 |
| 2005B | 24 | | GL | AE | 3-10 | 49-73-11 | D41660J | | 19 | | TB0207C | A121 | 2 | | 115-199 |
| 2005R | 24 | | GL | AE | 0-0 | 49-73-11 | D41660J | | 20 | | TB0207C | CAP | Y | | 115-199 |
| 2025B | 24 | | GL | AY | 3-8 | 24-34-11 | D40904J | | 8 | | TB0207Y | C043 | BJ | | 001-099 |
| 2025B | 24 | | GL | KM | 3-8 | 24-34-11 | D40904J | | 8 | | TB0207Y | C043 | BJ | | 115-199 |
| 2025R | 24 | | GL | AY | 0-0 | 24-34-11 | D40904J | | 7 | | TB0207Y | C044 | BJ | | 001-099 |
| 2025R | 24 | | GL | KM | 0-0 | 24-34-11 | D40904J | | 7 | | TB0207Y | C044 | BJ | | 115-199 |
| 2026B | 24 | | GL | AZ | 3-11 | 24-34-11 | D00321B | D07 | | | TB0207Y | C043 | BJ | | 001, 003-099 |
| 2026B | 24 | | GL | AZ | 4-0 | 24-34-11 | D00321B | D07 | | | TB0207Y | C043 | BJ | | 002 |
| 2026B | 24 | | GL | KN | 3-11 | 24-34-11 | D00321B | D07 | | | TB0207Y | C043 | BJ | | 115-199 |
| 2026R | 24 | | GL | AZ | 0-0 | 24-34-11 | D00321B | D06 | | | TB0207Y | C044 | BJ | | 001-099 |
| 2026R | 24 | | GL | KN | 0-0 | 24-34-11 | D00321B | D06 | | | TB0207Y | C044 | BJ | | 115-199 |
| 2027B | 24 | | GL | BA | 2-6 | 24-34-11 | D00319B | D07 | | | TB0207Y | C043 | BJ | | 001, 003-099 |
| 2027B | 24 | | GL | BA | 2-7 | 24-34-11 | D00319B | D07 | | | TB0207Y | C043 | BJ | | 002 |
| 2027B | 24 | | GL | KO | 2-7 | 24-34-11 | D00319B | D07 | | | TB0207Y | C043 | BJ | | 115-199 |
| 2027R | 24 | | GL | BA | 0-0 | 24-34-11 | D00319B | D06 | | | TB0207Y | C044 | BJ | | 001-099 |
| 2027R | 24 | | GL | KO | 0-0 | 24-34-11 | D00319B | D06 | | | TB0207Y | C044 | BJ | | 115-199 |
| 2028B | 24 | | GL | BB | 3-0 | 24-34-11 | D41660J | | 24 | | TB0207Y | C075 | BJ | | 001-099 |
| 2028B | 24 | | GL | KP | 3-2 | 24-34-11 | D41660J | | 24 | | TB0207Y | C075 | BJ | | 115-199 |
| 2028R | 24 | | GL | BB | 0-0 | 24-34-11 | D41660J | | 25 | | TB0207Y | C076 | BJ | | 001-099 |
| 2028R | 24 | | GL | KP | 0-0 | 24-34-11 | D41660J | | 25 | | TB0207Y | C076 | BJ | | 115-199 |
| 2029B | 24 | | GL | BC | 2-8 | 24-34-11 | D00319F | B01 | | | TB0207Y | C075 | BJ | | 001-099 |
| 2029B | 24 | | GL | KQ | 2-9 | 24-34-11 | D00319F | B01 | | | TB0207Y | C075 | BJ | | 115-199 |
| 2029R | 24 | | GL | BC | 0-0 | 24-34-11 | D00319F | B02 | | | TB0207Y | C076 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 94

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2029R | 24 | GL | KQ | | 0-0 | 24-34-11 | D00319F | | B02 | | TB0207Y | C076 | BJ | | 115-199 |
| 2030B | 24 | GL | BD | | 2-11 | 24-34-11 | D00321F | | B01 | | TB0207Y | C075 | BJ | | 001, 003-099 |
| 2030B | 24 | GL | BD | | 2-10 | 24-34-11 | D00321F | | B01 | | TB0207Y | C075 | BJ | | 002 |
| 2030B | 24 | GL | KR | | 3-0 | 24-34-11 | D00321F | | B01 | | TB0207Y | C075 | BJ | | 115-199 |
| 2030R | 24 | GL | BD | | 0-0 | 24-34-11 | D00321F | | B02 | | TB0207Y | C076 | BJ | | 001-099 |
| 2030R | 24 | GL | KR | | 0-0 | 24-34-11 | D00321F | | B02 | | TB0207Y | C076 | BJ | | 115-199 |
| 2031B | 24 | GL | BE | | 2-7 | 24-34-11 | D40892J | | 1 | | TB0207Y | A076 | BJ | | 001-099 |
| 2031B | 24 | GL | KS | | 2-8 | 24-34-11 | D40892J | | 1 | | TB0207Y | A076 | BJ | | 115-199 |
| 2031R | 24 | GL | BE | | 0-0 | 24-34-11 | D40892J | | 2 | | TB0207Y | A075 | BJ | | 001-099 |
| 2031R | 24 | GL | KS | | 0-0 | 24-34-11 | D40892J | | 2 | | TB0207Y | A075 | BJ | | 115-199 |
| 2032B | 24 | GL | BF | | 2-9 | 24-34-11 | D00319B | | D10 | | TB0207Y | A076 | BJ | | 001-099 |
| 2032B | 24 | GL | KT | | 2-11 | 24-34-11 | D00319B | | D10 | | TB0207Y | A076 | BJ | | 115-199 |
| 2032R | 24 | GL | BF | | 0-0 | 24-34-11 | D00319B | | D09 | | TB0207Y | A075 | BJ | | 001-099 |
| 2032R | 24 | GL | KT | | 0-0 | 24-34-11 | D00319B | | D09 | | TB0207Y | A075 | BJ | | 115-199 |
| 2033B | 24 | GL | BG | | 3-1 | 24-34-11 | D00321B | | D10 | | TB0207Y | A076 | BJ | | 001-099 |
| 2033B | 24 | GL | KU | | 3-2 | 24-34-11 | D00321B | | D10 | | TB0207Y | A076 | BJ | | 115-199 |
| 2033R | 24 | GL | BG | | 0-0 | 24-34-11 | D00321B | | D09 | | TB0207Y | A075 | BJ | | 001-099 |
| 2033R | 24 | GL | KU | | 0-0 | 24-34-11 | D00321B | | D09 | | TB0207Y | A075 | BJ | | 115-199 |
| 2034B | 24 | GL | BH | | 2-6 | 24-34-11 | D40892J | | 11 | | TB0207Y | C120 | BJ | | 001-099 |
| 2034B | 24 | GL | KV | | 2-5 | 24-34-11 | D40892J | | 11 | | TB0207Y | C120 | BJ | | 115-199 |
| 2034R | 24 | GL | BH | | 0-0 | 24-34-11 | D40892J | | 12 | | TB0207Y | C119 | BJ | | 001-099 |
| 2034R | 24 | GL | KV | | 0-0 | 24-34-11 | D40892J | | 12 | | TB0207Y | C119 | BJ | | 115-199 |
| 2035B | 24 | GL | BI | | 2-5 | 24-34-11 | D00321B | | D13 | | TB0207Y | C120 | BJ | | 001-099 |
| 2035B | 24 | GL | KW | | 2-4 | 24-34-11 | D00321B | | D13 | | TB0207Y | C120 | BJ | | 115-199 |
| 2035R | 24 | GL | BI | | 0-0 | 24-34-11 | D00321B | | D12 | | TB0207Y | C119 | BJ | | 001-099 |
| 2035R | 24 | GL | KW | | 0-0 | 24-34-11 | D00321B | | D12 | | TB0207Y | C119 | BJ | | 115-199 |
| 2036B | 24 | GL | BJ | | 3-8 | 24-34-11 | D00319B | | D13 | | TB0207Y | C120 | BJ | | 001-099 |
| 2036B | 24 | GL | KX | | 3-7 | 24-34-11 | D00319B | | D13 | | TB0207Y | C120 | BJ | | 115-199 |
| 2036R | 24 | GL | BJ | | 0-0 | 24-34-11 | D00319B | | D12 | | TB0207Y | C119 | BJ | | 001-099 |
| 2036R | 24 | GL | KX | | 0-0 | 24-34-11 | D00319B | | D12 | | TB0207Y | C119 | BJ | | 115-199 |
| 2039B | 24 | GL | BM | | 2-2 | 27-28-11 | D41628J | | 24 | | TB0207Y | C055 | BJ | | 001-099 |
| 2039B | 24 | GL | GJ | | 2-4 | 27-28-11 | D41628J | | 24 | | TB0207Y | C055 | BJ | | 115-199 |
| 2039R | 24 | GL | BM | | 0-0 | 27-28-11 | D41628J | | 25 | | GD02208 | ST.. | 2 | | 001-099 |
| 2039R | 24 | GL | GJ | | 0-0 | 27-28-11 | D41628J | | 25 | | GD02208 | ST.. | 2 | | 115-199 |
| 2040B | 20 | GB | BN | | 4-6 | 35-11-13 | GD02213 | | DC.. | 2 | D41369J | | 38 | | 001-099 |
| 2040B | 22 | GB | GM | | 4-7 | 35-11-13 | D41369J | | 38 | | GD02213 | DC.. | 2 | | 115-199 |
| 2040R | 20 | GB | BN | | 0-0 | 35-11-13 | D41369J | | 39 | | TB0207Y | A100 | BJ | | 001-099 |
| 2040R | 22 | GB | GM | | 0-0 | 35-11-13 | D41369J | | 39 | | TB0207Y | A100 | BJ | | 115-199 |
| 2043B | 24 | GL | BQ | | 3-5 | 27-28-13 | D40584J | | 30 | | D41628J | | 28 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 95

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2043B | 24 | GL | GN | | 3-7 | 27-28-13 | D40584J | | 30 | | D41628J | 28 | | | 115-199 |
| 2043R | 24 | GL | BQ | | 0-0 | 27-28-13 | D40584J | | 31 | | D41628J | 29 | | | 001-099 |
| 2043R | 24 | GL | GN | | 0-0 | 27-28-13 | D40584J | | 31 | | D41628J | 29 | | | 115-199 |
| 2044B | 24 | GL | BR | | 2-9 | 27-38-11 | D41632J | | 15 | | GD02208 | ST.. | 2 | | 001-099 |
| 2044B | 24 | GL | GH | | 2-10 | 27-38-11 | D41632J | | 15 | | GD02208 | ST.. | 2 | | 115-199 |
| 2044R | 24 | GL | BR | | 0-0 | 27-38-11 | D41632J | | 16 | | TB0207Y | A059 | BJ | | 001-099 |
| 2044R | 24 | GL | GH | | 0-0 | 27-38-11 | D41632J | | 16 | | TB0207Y | A059 | BJ | | 115-199 |
| 2045B | 24 | GL | BS | | 2-2 | 27-38-11 | D41628J | | 20 | | TB0207Y | C059 | BJ | | 001-099 |
| 2045B | 24 | GL | GI | | 2-4 | 27-38-11 | D41628J | | 20 | | TB0207Y | C059 | BJ | | 115-199 |
| 2045R | 24 | GL | BS | | 0-0 | 27-38-11 | D41628J | | 19 | | GD02208 | ST.. | 2 | | 001-099 |
| 2045R | 24 | GL | GI | | 0-0 | 27-38-11 | D41628J | | 19 | | GD02208 | ST.. | 2 | | 115-199 |
| 2048B | 24 | GL | BV | | 3-10 | 21-52-11 | D00319A | | F06 | | D42084J | 1 | | | 001-099 |
| 2048B | 24 | GL | GO | | 4-1 | 21-52-11 | D00319A | | F06 | | D42084J | 1 | | | 115-199 |
| 2048R | 24 | GL | BV | | 0-0 | 21-52-11 | D00319A | | F07 | | D42084J | 2 | | | 001-099 |
| 2048R | 24 | GL | GO | | 0-0 | 21-52-11 | D00319A | | F07 | | D42084J | 2 | | | 115-199 |
| 2049B | 24 | GL | BW | | 3-9 | 21-52-11 | D00319D | | D13 | | D42084J | 3 | | | 001-099 |
| 2049R | 24 | GL | BW | | 0-0 | 21-52-11 | D00319D | | D14 | | D42084J | 4 | | | 001-099 |
| 2050B | 24 | GL | BX | | 3-10 | 21-52-11 | D00319A | | E15 | | D42084J | 5 | | | 001-099 |
| 2050R | 24 | GL | BX | | 0-0 | 21-52-11 | D00319A | | D15 | | D42084J | 6 | | | 001-099 |
| 2051B | 24 | GL | BY | | 3-7 | 21-52-11 | D00319F | | A07 | | D42084J | 7 | | | 001-099 |
| 2051R | 24 | GL | BY | | 0-0 | 21-52-11 | D00319F | | A08 | | D42084J | 8 | | | 001-099 |
| 2052B | 24 | GL | BZ | | 3-10 | 21-52-11 | D00319A | | F14 | | D42084J | 9 | | | 001-099 |
| 2052R | 24 | GL | BZ | | 0-0 | 21-52-11 | D00319A | | E14 | | D42084J | 10 | | | 001-099 |
| 2053B | 24 | GL | CA | | 4-1 | 21-52-11 | D00321A | | F06 | | D42086J | 1 | | | 001-099 |
| 2053B | 24 | GL | GT | | 4-8 | 21-52-11 | D00321A | | F06 | | D42086J | 1 | | | 115-199 |
| 2053R | 24 | GL | CA | | 0-0 | 21-52-11 | D00321A | | F07 | | D42086J | 2 | | | 001-099 |
| 2053R | 24 | GL | GT | | 0-0 | 21-52-11 | D00321A | | F07 | | D42086J | 2 | | | 115-199 |
| 2054B | 24 | GL | CB | | 4-0 | 21-52-11 | D00321D | | D13 | | D42086J | 3 | | | 001-099 |
| 2054R | 24 | GL | CB | | 0-0 | 21-52-11 | D00321D | | D14 | | D42086J | 4 | | | 001-099 |
| 2055B | 24 | GL | CC | | 4-1 | 21-52-11 | D00321A | | E15 | | D42086J | 5 | | | 001-099 |
| 2055R | 24 | GL | CC | | 0-0 | 21-52-11 | D00321A | | D15 | | D42086J | 6 | | | 001-099 |
| 2056B | 24 | GL | CD | | 3-9 | 21-52-11 | D00321F | | A07 | | D42086J | 7 | | | 001-099 |
| 2056R | 24 | GL | CD | | 0-0 | 21-52-11 | D00321F | | A08 | | D42086J | 8 | | | 001-099 |
| 2057B | 24 | GL | CE | | 4-1 | 21-52-11 | D00321A | | F14 | | D42086J | 9 | | | 001-099 |
| 2057R | 24 | GL | CE | | 0-0 | 21-52-11 | D00321A | | E14 | | D42086J | 10 | | | 001-099 |
| 2062B | 24 | GL | CJ | | 3-8 | 21-52-31 | D04646A | | C06 | | D42086J | 18 | | | 001-099 |
| 2062B | 24 | GL | HY | | 3-1 | 21-52-31 | D04646A | | C06 | | D42086J | 18 | | | 115-199 |
| 2062R | 24 | GL | CJ | | 0-0 | 21-52-31 | D04646A | | C05 | | D42086J | 17 | | | 001-099 |
| 2062R | 24 | GL | HY | | 0-0 | 21-52-31 | D04646A | | C05 | | D42086J | 17 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 96

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2063B | 24 | GL | CK | | 3-8 | 21-52-31 | | D04646A | | B06 | | D42086J | 23 | | | 001-099 |
| 2063B | 24 | GL | IA | | 3-1 | 21-52-31 | | D04646A | | B06 | | D42086J | 23 | | | 115-199 |
| 2063R | 24 | GL | CK | | 0-0 | 21-52-31 | | D04646A | | B05 | | D42086J | 22 | | | 001-099 |
| 2063R | 24 | GL | IA | | 0-0 | 21-52-31 | | D04646A | | B05 | | D42086J | 22 | | | 115-199 |
| 2064B | 24 | GL | CL | | 2-1 | 21-52-31 | | D04646B | | C06 | | D42084J | 18 | | | 001-099 |
| 2064B | 24 | GL | IB | | 2-4 | 21-52-31 | | D04646B | | C06 | | D42084J | 18 | | | 115-199 |
| 2064R | 24 | GL | CL | | 0-0 | 21-52-31 | | D04646B | | C05 | | D42084J | 17 | | | 001-099 |
| 2064R | 24 | GL | IB | | 0-0 | 21-52-31 | | D04646B | | C05 | | D42084J | 17 | | | 115-199 |
| 2065B | 24 | GL | CM | | 2-1 | 21-52-31 | | D04646B | | B06 | | D42084J | 23 | | | 001-099 |
| 2065B | 24 | GL | ID | | 2-4 | 21-52-31 | | D04646B | | B06 | | D42084J | 23 | | | 115-199 |
| 2065R | 24 | GL | CM | | 0-0 | 21-52-31 | | D04646B | | B05 | | D42084J | 22 | | | 001-099 |
| 2065R | 24 | GL | ID | | 0-0 | 21-52-31 | | D04646B | | B05 | | D42084J | 22 | | | 115-199 |
| 2068B | 24 | GL | CP | | 4-0 | 21-65-12 | | D42086J | | 50 | | D00321D | D09 | | | 001-099 |
| 2068B | 24 | GL | IH | | 4-7 | 21-65-12 | | D00321D | | D09 | | D42086J | 50 | | | 115-199 |
| 2068R | 24 | GL | CP | | 0-0 | 21-65-12 | | D42086J | | 51 | | D00321D | D10 | | | 001-099 |
| 2068R | 24 | GL | IH | | 0-0 | 21-65-12 | | D00321D | | D10 | | D42086J | 51 | | | 115-199 |
| 2069B | 24 | GL | CQ | | 4-0 | 21-65-12 | | D42086J | | 52 | | D00321D | D11 | | | 001-099 |
| 2069B | 24 | GL | II | | 4-7 | 21-65-12 | | D00321D | | D11 | | D42086J | 52 | | | 115-199 |
| 2069R | 24 | GL | CQ | | 0-0 | 21-65-12 | | D42086J | | 53 | | D00321D | D12 | | | 001-099 |
| 2069R | 24 | GL | II | | 0-0 | 21-65-12 | | D00321D | | D12 | | D42086J | 53 | | | 115-199 |
| 2070B | 24 | GL | CR | | 2-8 | 21-65-12 | | D42086J | | 54 | | D00319D | D11 | | | 001-099 |
| 2070B | 24 | GL | IJ | | 3-3 | 21-65-12 | | D00319D | | D11 | | D42086J | 54 | | | 115-199 |
| 2070R | 24 | GL | CR | | 0-0 | 21-65-12 | | D42086J | | 55 | | D00319D | D12 | | | 001-099 |
| 2070R | 24 | GL | IJ | | 0-0 | 21-65-12 | | D00319D | | D12 | | D42086J | 55 | | | 115-199 |
| 2071B | 24 | GL | CS | | 3-9 | 36-22-21 | | D42084J | | 26 | | D00319D | H14 | | | 001-099 |
| 2071B | 24 | GL | IK | | 4-0 | 36-22-21 | | D00319D | | H14 | | D42084J | 26 | | | 115-199 |
| 2071R | 24 | GL | CS | | 0-0 | 36-22-21 | | D42084J | | 27 | | D00319D | H15 | | | 001-099 |
| 2071R | 24 | GL | IK | | 0-0 | 36-22-21 | | D00319D | | H15 | | D42084J | 27 | | | 115-199 |
| 2072B | 24 | GL | CT | | 4-0 | 36-22-21 | | D42086J | | 26 | | D00321D | H14 | | | 001-099 |
| 2072B | 24 | GL | IL | | 4-7 | 36-22-21 | | D00321D | | H14 | | D42086J | 26 | | | 115-199 |
| 2072R | 24 | GL | CT | | 0-0 | 36-22-21 | | D42086J | | 27 | | D00321D | H15 | | | 001-099 |
| 2072R | 24 | GL | IL | | 0-0 | 36-22-21 | | D00321D | | H15 | | D42086J | 27 | | | 115-199 |
| 2073B | 24 | GL | CU | | 3-6 | 29-32-41 | | D41736J | | 23 | | D00321B | J05 | | | 001-099 |
| 2073B | 24 | GL | QA | | 3-6 | 29-32-41 | | D00321B | | J05 | | D41736J | 23 | | | 115-199 |
| 2073R | 24 | GL | CU | | 0-0 | 29-32-41 | | D41736J | | 21 | | D00321B | J04 | | | 001-099 |
| 2073R | 24 | GL | QA | | 0-0 | 29-32-41 | | D00321B | | J04 | | D41736J | 21 | | | 115-199 |
| 2074B | 24 | GL | CV | | 4-1 | 29-32-41 | | D41792J | | 7 | | D00319D | D05 | | | 001-099 |
| 2074B | 24 | GL | QB | | 4-3 | 29-32-41 | | D00319D | | D05 | | D41792J | 7 | | | 115-199 |
| 2074R | 24 | GL | CV | | 0-0 | 29-32-41 | | D41792J | | 6 | | D00319D | D04 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 97

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2074R | 24 | GL | QB | | 0-0 | 29-32-41 | D00319D | | D04 | | D41792J | 6 | | | 115-199 |
| 2075B | 24 | GL | CW | | 2-7 | 29-32-41 | D41879J | | 32 | | D00319B | J05 | | | 001-099 |
| 2075B | 24 | GL | QC | | 2-7 | 29-32-41 | D00319B | | J05 | | D41879J | 32 | | | 115-199 |
| 2075R | 24 | GL | CW | | 0-0 | 29-32-41 | D41879J | | 31 | | D00319B | J04 | | | 001-099 |
| 2075R | 24 | GL | QC | | 0-0 | 29-32-41 | D00319B | | J04 | | D41879J | 31 | | | 115-199 |
| 2076B | 24 | GL | CX | | 3-7 | 21-52-11 | D00319F | | C01 | | D42084J | 32 | | | 001-099 |
| 2076R | 24 | GL | CX | | 0-0 | 21-52-11 | D00319F | | D01 | | D42084J | 33 | | | 001-099 |
| 2077B | 24 | GL | CY | | 3-9 | 21-52-11 | D00321F | | C01 | | D42086J | 32 | | | 001-099 |
| 2077R | 24 | GL | CY | | 0-0 | 21-52-11 | D00321F | | D01 | | D42086J | 33 | | | 001-099 |
| 2501B | 24 | G2 | EA | | 2-8 | 77-12-31 | D41788J | | 8 | | TB0207Z | 9 | BJ | | 001, 003-099 |
| 2501B | 24 | G2 | EA | | 2-9 | 77-12-31 | D41788J | | 8 | | TB0207Z | 9 | BJ | | 002 |
| 2501B | 24 | G2 | AM | | 5-3 | 77-12-31 | D41788J | | 8 | | TB0207Z | 9 | BJ | | 115-199 |
| 2501R | 24 | G2 | EA | | 0-0 | 77-12-31 | D41788J | | 9 | | TB0207Z | 10 | BJ | | 001-099 |
| 2501R | 24 | G2 | AM | | 0-0 | 77-12-31 | D41788J | | 9 | | TB0207Z | 10 | BJ | | 115-199 |
| 2501Z | | | EA | | 0-0 | 77-12-31 | D41788J | | 10 | | TB0207Z | | | TE | 001-099 |
| 2501Z | | | AM | | 0-0 | 77-12-31 | D41788J | | 10 | | TB0207Z | | | JF | 115-199 |
| 2502B | 24 | G2 | EB | | 2-7 | 77-12-31 | D42041J | | 8 | | TB0207Z | 9 | BJ | | 001, 003-099 |
| 2502B | 24 | G2 | EB | | 2-8 | 77-12-31 | D42041J | | 8 | | TB0207Z | 9 | BJ | | 002 |
| 2502B | 24 | G2 | AN | | 2-6 | 77-12-31 | D42041J | | 30 | | TB0207Z | 9 | BJ | | 115-199 |
| 2502R | 24 | G2 | EB | | 0-0 | 77-12-31 | D42041J | | 7 | | TB0207Z | 10 | BJ | | 001-099 |
| 2502R | 24 | G2 | AN | | 0-0 | 77-12-31 | D42041J | | 29 | | TB0207Z | 10 | BJ | | 115-199 |
| 2502Z | | | EB | | 0-0 | 77-12-31 | D42041J | | 9 | | TB0207Z | | | TE | 001-099 |
| 2502Z | | | AN | | 0-0 | 77-12-31 | D42041J | | 31 | | TB0207Z | | | JF | 115-199 |
| 2503B | 24 | G2 | EC | | 4-10 | 77-12-31 | D00321D | | E08 | | TB0207Z | 9 | BJ | | 001, 003-099 |
| 2503B | 24 | G2 | EC | | 4-11 | 77-12-31 | D00321D | | E08 | | TB0207Z | 9 | BJ | | 002 |
| 2503B | 24 | G2 | AO | | 4-9 | 77-12-31 | D00321D | | E08 | | TB0207Z | 9 | BJ | | 115-199 |
| 2503R | 24 | G2 | EC | | 0-0 | 77-12-31 | D00321D | | A07 | | TB0207Z | 10 | BJ | | 001-099 |
| 2503R | 24 | G2 | AO | | 0-0 | 77-12-31 | D00321D | | A07 | | TB0207Z | 10 | BJ | | 115-199 |
| 2503Z | | | EC | | 0-0 | 77-12-31 | D00321D | | DED | | TB0207Z | | | TE | 001-099 |
| 2503Z | | | AO | | 0-0 | 77-12-31 | D00321D | | DED | | TB0207Z | | | JF | 115-199 |
| 2504B | 24 | G2 | ED | | 3-6 | 77-12-31 | D00319D | | E08 | | TB0207Z | 9 | BJ | | 001, 003-099 |
| 2504B | 24 | G2 | ED | | 3-7 | 77-12-31 | D00319D | | E08 | | TB0207Z | 9 | BJ | | 002 |
| 2504B | 24 | G2 | AP | | 3-6 | 77-12-31 | D00319D | | E08 | | TB0207Z | 9 | BJ | | 115-199 |
| 2504R | 24 | G2 | ED | | 0-0 | 77-12-31 | D00319D | | A07 | | TB0207Z | 10 | BJ | | 001-099 |
| 2504R | 24 | G2 | AP | | 0-0 | 77-12-31 | D00319D | | A07 | | TB0207Z | 10 | BJ | | 115-199 |
| 2504Z | | | ED | | 0-0 | 77-12-31 | D00319D | | DED | | TB0207Z | | | TE | 001-099 |
| 2504Z | | | AP | | 0-0 | 77-12-31 | D00319D | | DED | | TB0207Z | | | JF | 115-199 |
| 2505B | 24 | G2 | EE | | 3-6 | 77-12-31 | D42023J | | 1 | | TB0207Z | 16 | BJ | | 001-099 |
| 2505B | 24 | G2 | AQ | | 3-5 | 77-12-31 | D42023J | | 4 | | TB0207Z | 16 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 98

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|-------------|------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2505R | 24 | G2 | EE | | 0-0 | 77-12-31 | D42023J | | 2 | | TB0207Z | 15 | BJ | | 001-099 |
| 2505R | 24 | G2 | AQ | | 0-0 | 77-12-31 | D42023J | | 5 | | TB0207Z | 15 | BJ | | 115-199 |
| 2505Z | | | EE | | 0-0 | 77-12-31 | D42023J | | 3 | | TB0207Z | | | TC | 001-099 |
| 2505Z | | | AQ | | 0-0 | 77-12-31 | D42023J | | 6 | | TB0207Z | | | JE | 115-199 |
| 2506B | 24 | G2 | EF | | 2-9 | 77-12-31 | D41772J | | 9 | | TB0207Z | 16 | BJ | | 001-099 |
| 2506B | 24 | G2 | AR | | 2-7 | 77-12-31 | D41772J | | 9 | | TB0207Z | 16 | BJ | | 115-199 |
| 2506R | 24 | G2 | EF | | 0-0 | 77-12-31 | D41772J | | 8 | | TB0207Z | 15 | BJ | | 001-099 |
| 2506R | 24 | G2 | AR | | 0-0 | 77-12-31 | D41772J | | 8 | | TB0207Z | 15 | BJ | | 115-199 |
| 2506Z | | | EF | | 0-0 | 77-12-31 | D41772J | | 10 | | TB0207Z | | | TC | 001-099 |
| 2506Z | | | AR | | 0-0 | 77-12-31 | D41772J | | 10 | | TB0207Z | | | JE | 115-199 |
| 2507B | 24 | G2 | EG | | 3-7 | 77-12-31 | D00319A | | D12 | | TB0207Z | 16 | BJ | | 001-099 |
| 2507B | 24 | G2 | AS | | 3-6 | 77-12-31 | D00319A | | D12 | | TB0207Z | 16 | BJ | | 115-199 |
| 2507R | 24 | G2 | EG | | 0-0 | 77-12-31 | D00319A | | F11 | | TB0207Z | 15 | BJ | | 001-099 |
| 2507R | 24 | G2 | AS | | 0-0 | 77-12-31 | D00319A | | F11 | | TB0207Z | 15 | BJ | | 115-199 |
| 2507Z | | | EG | | 0-0 | 77-12-31 | D00319A | | DED | | TB0207Z | | | TC | 001-099 |
| 2507Z | | | AS | | 0-0 | 77-12-31 | D00319A | | DED | | TB0207Z | | | JE | 115-199 |
| 2508B | 24 | G2 | EH | | 5-0 | 77-12-31 | D00321A | | D12 | | TB0207Z | 16 | BJ | | 001-099 |
| 2508B | 24 | G2 | AT | | 4-10 | 77-12-31 | D00321A | | D12 | | TB0207Z | 16 | BJ | | 115-199 |
| 2508R | 24 | G2 | EH | | 0-0 | 77-12-31 | D00321A | | F11 | | TB0207Z | 15 | BJ | | 001-099 |
| 2508R | 24 | G2 | AT | | 0-0 | 77-12-31 | D00321A | | F11 | | TB0207Z | 15 | BJ | | 115-199 |
| 2508Z | | | EH | | 0-0 | 77-12-31 | D00321A | | DED | | TB0207Z | | | TC | 001-099 |
| 2508Z | | | AT | | 0-0 | 77-12-31 | D00321A | | DED | | TB0207Z | | | JE | 115-199 |
| 2509B | 24 | G2 | EI | | 2-6 | 77-12-11 | D42093J | | 14 | | TB0207Z | 107 | BJ | | 001, 003-099 |
| 2509B | 24 | G2 | EI | | 2-7 | 77-12-11 | D42093J | | 14 | | TB0207Z | 107 | BJ | | 002 |
| 2509B | 24 | G2 | AU | | 2-7 | 77-12-11 | D42093J | | 5 | | TB0207Z | 107 | BJ | | 115-199 |
| 2509R | 24 | G2 | EI | | 0-0 | 77-12-11 | D42093J | | 13 | | TB0207Z | 106 | BJ | | 001-099 |
| 2509R | 24 | G2 | AU | | 0-0 | 77-12-11 | D42093J | | 4 | | TB0207Z | 106 | BJ | | 115-199 |
| 2509Z | | | EI | | 0-0 | 77-12-11 | D42093J | | 15 | | TB0207Z | | | RU | 001-099 |
| 2509Z | | | AU | | 0-0 | 77-12-11 | D42093J | | 6 | | TB0207Z | | | SA | 115-199 |
| 2510B | 24 | G2 | EJ | | 2-9 | 77-12-11 | D41774J | | 5 | | TB0207Z | 107 | BJ | | 001-099 |
| 2510B | 24 | G2 | AV | | 2-5 | 77-12-11 | D41774J | | 5 | | TB0207Z | 107 | BJ | | 115-199 |
| 2510R | 24 | G2 | EJ | | 0-0 | 77-12-11 | D41774J | | 4 | | TB0207Z | 106 | BJ | | 001-099 |
| 2510R | 24 | G2 | AV | | 0-0 | 77-12-11 | D41774J | | 4 | | TB0207Z | 106 | BJ | | 115-199 |
| 2510Z | | | EJ | | 0-0 | 77-12-11 | D41774J | | 6 | | TB0207Z | | | RU | 001-099 |
| 2510Z | | | AV | | 0-0 | 77-12-11 | D41774J | | 6 | | TB0207Z | | | SA | 115-199 |
| 2511B | 24 | G2 | EK | | 2-6 | 77-12-11 | D00321E | | B14 | | TB0207Y | C109 | BJ | | 001, 003-099 |
| 2511B | 24 | G2 | EK | | 2-7 | 77-12-11 | D00321E | | B14 | | TB0207Y | C109 | BJ | | 002 |
| 2511B | 24 | G2 | AW | | 2-6 | 77-12-11 | D00321E | | B14 | | TB0207Y | C109 | BJ | | 115-199 |
| 2511R | 24 | G2 | EK | | 0-0 | 77-12-11 | D00321E | | A14 | | TB0207Y | A109 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 99

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2511R | 24 | G2 | AW | | 0-0 | 77-12-11 | D00321E | A14 | | | TB0207Y | A109 | BJ | | 115-199 |
| 2511Z | | | EK | | 0-0 | 77-12-11 | D00321E | DED | | | TB0207Y | | | TA | 001-099 |
| 2511Z | | | AW | | 0-0 | 77-12-11 | D00321E | DED | | | TB0207Y | | | SC | 115-199 |
| 2512B | 24 | G2 | EL | | 3-8 | 77-12-11 | D00319E | B14 | | | TB0207Y | C109 | BJ | | 001-099 |
| 2512B | 24 | G2 | AZ | | 3-7 | 77-12-11 | D00319E | B14 | | | TB0207Y | C109 | BJ | | 115-199 |
| 2512R | 24 | G2 | EL | | 0-0 | 77-12-11 | D00319E | A14 | | | TB0207Y | A109 | BJ | | 001-099 |
| 2512R | 24 | G2 | AZ | | 0-0 | 77-12-11 | D00319E | A14 | | | TB0207Y | A109 | BJ | | 115-199 |
| 2512Z | | | EL | | 0-0 | 77-12-11 | D00319E | DED | | | TB0207Y | | | TA | 001-099 |
| 2512Z | | | AZ | | 0-0 | 77-12-11 | D00319E | DED | | | TB0207Y | | | SC | 115-199 |
| 2513B | 24 | G2 | EM | | 3-3 | 77-12-11 | D42073J | 22 | | | TB0207Z | 112 | BJ | | 001, 003-099 |
| 2513B | 24 | G2 | EM | | 3-4 | 77-12-11 | D42073J | 22 | | | TB0207Z | 112 | BJ | | 002 |
| 2513B | 24 | G2 | AX | | 3-5 | 77-12-11 | D42073J | 19 | | | TB0207Z | 112 | BJ | | 115-199 |
| 2513R | 24 | G2 | EM | | 0-0 | 77-12-11 | D42073J | 21 | | | TB0207Z | 111 | BJ | | 001-099 |
| 2513R | 24 | G2 | AX | | 0-0 | 77-12-11 | D42073J | 18 | | | TB0207Z | 111 | BJ | | 115-199 |
| 2513Z | | | EM | | 0-0 | 77-12-11 | D42073J | 23 | | | TB0207Z | | | RN | 001-099 |
| 2513Z | | | AX | | 0-0 | 77-12-11 | D42073J | 20 | | | TB0207Z | | | SB | 115-199 |
| 2514B | 24 | G2 | EN | | 3-3 | 77-12-11 | D41764J | 4 | | | TB0207Z | 112 | BJ | | 001, 003-099 |
| 2514B | 24 | G2 | EN | | 3-4 | 77-12-11 | D41764J | 4 | | | TB0207Z | 112 | BJ | | 002 |
| 2514B | 24 | G2 | AY | | 4-7 | 77-12-11 | D41764J | 4 | | | TB0207Z | 112 | BJ | | 115-199 |
| 2514R | 24 | G2 | EN | | 0-0 | 77-12-11 | D41764J | 3 | | | TB0207Z | 111 | BJ | | 001-099 |
| 2514R | 24 | G2 | AY | | 0-0 | 77-12-11 | D41764J | 3 | | | TB0207Z | 111 | BJ | | 115-199 |
| 2514Z | | | EN | | 0-0 | 77-12-11 | D41764J | 5 | | | TB0207Z | | | RN | 001-099 |
| 2514Z | | | AY | | 0-0 | 77-12-11 | D41764J | 5 | | | TB0207Z | | | SB | 115-199 |
| 2515B | 24 | G2 | EO | | 2-5 | 77-12-11 | D00321B | D02 | | | TB0207Y | C110 | BJ | | 001-099 |
| 2515B | 24 | G2 | BA | | 2-4 | 77-12-11 | D00321B | D02 | | | TB0207Y | C110 | BJ | | 115-199 |
| 2515R | 24 | G2 | EO | | 0-0 | 77-12-11 | D00321B | D01 | | | TB0207Y | A110 | BJ | | 001-099 |
| 2515R | 24 | G2 | BA | | 0-0 | 77-12-11 | D00321B | D01 | | | TB0207Y | A110 | BJ | | 115-199 |
| 2515Z | | | EO | | 0-0 | 77-12-11 | D00321B | DED | | | TB0207Y | | | TB | 001-099 |
| 2515Z | | | BA | | 0-0 | 77-12-11 | D00321B | DED | | | TB0207Y | | | SD | 115-199 |
| 2516B | 24 | G2 | EP | | 3-7 | 77-12-11 | D00319B | D02 | | | TB0207Y | C110 | BJ | | 001, 003-099 |
| 2516B | 24 | G2 | EP | | 3-8 | 77-12-11 | D00319B | D02 | | | TB0207Y | C110 | BJ | | 002 |
| 2516B | 24 | G2 | BB | | 3-7 | 77-12-11 | D00319B | D02 | | | TB0207Y | C110 | BJ | | 115-199 |
| 2516R | 24 | G2 | EP | | 0-0 | 77-12-11 | D00319B | D01 | | | TB0207Y | A110 | BJ | | 001-099 |
| 2516R | 24 | G2 | BB | | 0-0 | 77-12-11 | D00319B | D01 | | | TB0207Y | A110 | BJ | | 115-199 |
| 2516Z | | | EP | | 0-0 | 77-12-11 | D00319B | DED | | | TB0207Y | | | TB | 001-099 |
| 2516Z | | | BB | | 0-0 | 77-12-11 | D00319B | DED | | | TB0207Y | | | SD | 115-199 |
| 2517B | 24 | G2 | EQ | | 4-7 | 77-12-21 | D41774J | 8 | | | TB0207Y | A007 | BJ | | 001, 003-099 |
| 2517B | 24 | G2 | EQ | | 4-8 | 77-12-21 | D41774J | 8 | | | TB0207Y | A007 | BJ | | 002 |
| 2517B | 24 | G2 | BC | | 5-0 | 77-12-21 | D41774J | 8 | | | TB0207Y | A007 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 100

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2517R | 24 | G2 | EQ | | 0-0 | 77-12-21 | D41774J | | 7 | | TB0207Y | A008 | BJ | | 001-099 |
| 2517R | 24 | G2 | BC | | 0-0 | 77-12-21 | D41774J | | 7 | | TB0207Y | A008 | BJ | | 115-199 |
| 2517Z | | | EQ | | 0-0 | 77-12-21 | D41774J | | 9 | | TB0207Y | | | TG | 001-099 |
| 2517Z | | | BC | | 0-0 | 77-12-21 | D41774J | | 9 | | TB0207Y | | | TG | 115-199 |
| 2518B | 24 | G2 | ER | | 4-11 | 77-12-21 | D00321D | | J09 | | TB0207Y | A007 | BJ | | 001-099 |
| 2518B | 24 | G2 | BD | | 4-9 | 77-12-21 | D00321D | | J09 | | TB0207Y | A007 | BJ | | 115-199 |
| 2518R | 24 | G2 | ER | | 0-0 | 77-12-21 | D00321D | | J08 | | TB0207Y | A008 | BJ | | 001-099 |
| 2518R | 24 | G2 | BD | | 0-0 | 77-12-21 | D00321D | | J08 | | TB0207Y | A008 | BJ | | 115-199 |
| 2518Z | | | ER | | 0-0 | 77-12-21 | D00321D | | DED | | TB0207Y | | | TG | 001-099 |
| 2518Z | | | BD | | 0-0 | 77-12-21 | D00321D | | DED | | TB0207Y | | | TG | 115-199 |
| 2519B | 24 | G2 | ES | | 3-6 | 77-12-21 | D00319D | | J09 | | TB0207Y | A007 | BJ | | 001, 003-099 |
| 2519B | 24 | G2 | ES | | 3-7 | 77-12-21 | D00319D | | J09 | | TB0207Y | A007 | BJ | | 002 |
| 2519B | 24 | G2 | BE | | 3-6 | 77-12-21 | D00319D | | J09 | | TB0207Y | A007 | BJ | | 115-199 |
| 2519R | 24 | G2 | ES | | 0-0 | 77-12-21 | D00319D | | J08 | | TB0207Y | A008 | BJ | | 001-099 |
| 2519R | 24 | G2 | BE | | 0-0 | 77-12-21 | D00319D | | J08 | | TB0207Y | A008 | BJ | | 115-199 |
| 2519Z | | | ES | | 0-0 | 77-12-21 | D00319D | | DED | | TB0207Y | | | TG | 001-099 |
| 2519Z | | | BE | | 0-0 | 77-12-21 | D00319D | | DED | | TB0207Y | | | TG | 115-199 |
| 2520B | 24 | G2 | ET | | 3-7 | 77-12-21 | D41764J | | 7 | | TB0207Y | C007 | BJ | | 001-099 |
| 2520B | 24 | G2 | BF | | 2-8 | 77-12-21 | D41764J | | 7 | | TB0207Y | C007 | BJ | | 115-199 |
| 2520R | 24 | G2 | ET | | 0-0 | 77-12-21 | D41764J | | 6 | | TB0207Y | C008 | BJ | | 001-099 |
| 2520R | 24 | G2 | BF | | 0-0 | 77-12-21 | D41764J | | 6 | | TB0207Y | C008 | BJ | | 115-199 |
| 2520Z | | | ET | | 0-0 | 77-12-21 | D41764J | | 8 | | TB0207Y | | | TF | 001-099 |
| 2520Z | | | BF | | 0-0 | 77-12-21 | D41764J | | 8 | | TB0207Y | | | TF | 115-199 |
| 2521B | 24 | G2 | EU | | 3-7 | 77-12-21 | D00319A | | J05 | | TB0207Y | C007 | BJ | | 001-099 |
| 2521B | 24 | G2 | BG | | 3-6 | 77-12-21 | D00319A | | J05 | | TB0207Y | C007 | BJ | | 115-199 |
| 2521R | 24 | G2 | EU | | 0-0 | 77-12-21 | D00319A | | J06 | | TB0207Y | C008 | BJ | | 001-099 |
| 2521R | 24 | G2 | BG | | 0-0 | 77-12-21 | D00319A | | J06 | | TB0207Y | C008 | BJ | | 115-199 |
| 2521Z | | | EU | | 0-0 | 77-12-21 | D00319A | | DED | | TB0207Y | | | TF | 001-099 |
| 2521Z | | | BG | | 0-0 | 77-12-21 | D00319A | | DED | | TB0207Y | | | TF | 115-199 |
| 2522B | 24 | G2 | EV | | 5-0 | 77-12-21 | D00321A | | J05 | | TB0207Y | C007 | BJ | | 001-099 |
| 2522B | 24 | G2 | BH | | 4-10 | 77-12-21 | D00321A | | J05 | | TB0207Y | C007 | BJ | | 115-199 |
| 2522R | 24 | G2 | EV | | 0-0 | 77-12-21 | D00321A | | J06 | | TB0207Y | C008 | BJ | | 001-099 |
| 2522R | 24 | G2 | BH | | 0-0 | 77-12-21 | D00321A | | J06 | | TB0207Y | C008 | BJ | | 115-199 |
| 2522Z | | | EV | | 0-0 | 77-12-21 | D00321A | | DED | | TB0207Y | | | TF | 001-099 |
| 2522Z | | | BH | | 0-0 | 77-12-21 | D00321A | | DED | | TB0207Y | | | TF | 115-199 |
| 2523B | 24 | G2 | EW | | 3-6 | 79-34-11 | D00321D | | H10 | | D41736J | 14 | | | 001-099 |
| 2523B | 24 | G2 | BU | | 3-6 | 79-34-11 | D00321D | | H10 | | D41736J | 14 | | | 115-199 |
| 2523R | 24 | G2 | EW | | 0-0 | 79-34-11 | D00321D | | H09 | | D41736J | 15 | | | 001-099 |
| 2523R | 24 | G2 | BU | | 0-0 | 79-34-11 | D00321D | | H09 | | D41736J | 15 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 101

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1275 | 286N1275 | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | | |
| 2523Z | | EW | 0-0 | 79-34-11 | D00321D | DED | | | D41736J | | | AA | 001-099 | | |
| 2523Z | | BU | 0-0 | 79-34-11 | D00321D | DED | | | D41736J | | | AA | 115-199 | | |
| 2524B | 24 | G2 EX | 2-11 | 79-34-11 | D00319A | H10 | | | D41734J | 14 | | | 001-099 | | |
| 2524B | 24 | G2 BV | 3-0 | 79-34-11 | D00319A | H10 | | | D41734J | 14 | | | 115-199 | | |
| 2524R | 24 | G2 EX | 0-0 | 79-34-11 | D00319A | H11 | | | D41734J | 15 | | | 001-099 | | |
| 2524R | 24 | G2 BV | 0-0 | 79-34-11 | D00319A | H11 | | | D41734J | 15 | | | 115-199 | | |
| 2524Z | | EX | 0-0 | 79-34-11 | D00319A | DED | | | D41734J | | | AG | 001-099 | | |
| 2524Z | | BV | 0-0 | 79-34-11 | D00319A | DED | | | D41734J | | | AG | 115-199 | | |
| 2529T | 24 | BV FC | 3-1 | 31-41-11 | D00319A | C12 | | | D00789 | 1 | | | 001-099 | | |
| 2529T | 24 | BV DU | 3-2 | 31-41-11 | D00319A | C12 | | | D00789 | 1 | | | 115-199 | | |
| 2529W | 24 | BV FC | 0-0 | 31-41-11 | D00319A | C13 | | | D00789 | 2 | | | 001-099 | | |
| 2529W | 24 | BV DU | 0-0 | 31-41-11 | D00319A | C13 | | | D00789 | 2 | | | 115-199 | | |
| 2529Z | | FC | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AD | 001-099 | | |
| 2529Z | | DU | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AD | 115-199 | | |
| 2530T | 24 | BV FD | 3-1 | 31-41-11 | D00319A | B04 | | | D00789 | 7 | | | 001-099 | | |
| 2530T | 24 | BV DV | 3-2 | 31-41-11 | D00319A | B04 | | | D00789 | 7 | | | 115-199 | | |
| 2530W | 24 | BV FD | 0-0 | 31-41-11 | D00319A | A04 | | | D00789 | 8 | | | 001-099 | | |
| 2530W | 24 | BV DV | 0-0 | 31-41-11 | D00319A | A04 | | | D00789 | 8 | | | 115-199 | | |
| 2530Z | | FD | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AE | 001-099 | | |
| 2530Z | | DV | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AE | 115-199 | | |
| 2531T | 24 | BV FE | 3-1 | 31-41-11 | D00319A | C14 | | | D00789 | 13 | | | 001-099 | | |
| 2531T | 24 | BV DW | 3-2 | 31-41-11 | D00319A | C14 | | | D00789 | 13 | | | 115-199 | | |
| 2531W | 24 | BV FE | 0-0 | 31-41-11 | D00319A | C15 | | | D00789 | 14 | | | 001-099 | | |
| 2531W | 24 | BV DW | 0-0 | 31-41-11 | D00319A | C15 | | | D00789 | 14 | | | 115-199 | | |
| 2531Z | | FE | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AF | 001-099 | | |
| 2531Z | | DW | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AF | 115-199 | | |
| 2532T | 24 | BV FF | 3-1 | 31-41-11 | D00319A | B05 | | | D00789 | 19 | | | 001-099 | | |
| 2532T | 24 | BV DX | 3-2 | 31-41-11 | D00319A | B05 | | | D00789 | 19 | | | 115-199 | | |
| 2532W | 24 | BV FF | 0-0 | 31-41-11 | D00319A | A05 | | | D00789 | 20 | | | 001-099 | | |
| 2532W | 24 | BV DX | 0-0 | 31-41-11 | D00319A | A05 | | | D00789 | 20 | | | 115-199 | | |
| 2532Z | | FF | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AI | 001-099 | | |
| 2532Z | | DX | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AI | 115-199 | | |
| 2533T | 24 | BV FG | 3-1 | 31-41-11 | D00319A | C01 | | | D00789 | 25 | | | 001-099 | | |
| 2533T | 24 | BV DY | 3-2 | 31-41-11 | D00319A | C01 | | | D00789 | 25 | | | 115-199 | | |
| 2533W | 24 | BV FG | 0-0 | 31-41-11 | D00319A | C02 | | | D00789 | 26 | | | 001-099 | | |
| 2533W | 24 | BV DY | 0-0 | 31-41-11 | D00319A | C02 | | | D00789 | 26 | | | 115-199 | | |
| 2533Z | | FG | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AJ | 001-099 | | |
| 2533Z | | DY | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | D00789 | | | AJ | 115-199 | | |
| 2534T | 24 | BV FH | 3-0 | 31-41-11 | D00319B | A01 | | | D00789 | 31 | | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 102

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------------|----------|---------|------|------|--------|-------|--------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | |
| 2534T | 24 | BV | DZ | | 3-1 | 31-41-11 | D00319B | A01 | | | | D00789 | 31 | | | 115-199 | |
| 2534W | 24 | BV | FH | | 0-0 | 31-41-11 | D00319B | B01 | | | | D00789 | 32 | | | 001-099 | |
| 2534W | 24 | BV | DZ | | 0-0 | 31-41-11 | D00319B | B01 | | | | D00789 | 32 | | | 115-199 | |
| 2534Z | | | FH | | 0-0 | 31-41-11 | GD02218 | ST.. | 2 | | | D00789 | | | AK | 001-099 | |
| 2534Z | | | DZ | | 0-0 | 31-41-11 | GD02218 | ST.. | 2 | | | D00789 | | | AK | 115-199 | |
| 2535T | 24 | BV | FI | | 3-0 | 31-41-11 | D00319B | A02 | | | | D00789 | 37 | | | 001-099 | |
| 2535T | 24 | BV | EA | | 3-1 | 31-41-11 | D00319B | A02 | | | | D00789 | 37 | | | 115-199 | |
| 2535W | 24 | BV | FI | | 0-0 | 31-41-11 | D00319B | B02 | | | | D00789 | 38 | | | 001-099 | |
| 2535W | 24 | BV | EA | | 0-0 | 31-41-11 | D00319B | B02 | | | | D00789 | 38 | | | 115-199 | |
| 2535Z | | | FI | | 0-0 | 31-41-11 | GD02218 | ST.. | 2 | | | D00789 | | | AL | 001-099 | |
| 2535Z | | | EA | | 0-0 | 31-41-11 | GD02218 | ST.. | 2 | | | D00789 | | | AL | 115-199 | |
| 2536T | 24 | BV | FJ | | 3-1 | 31-41-11 | D00319A | C10 | | | | D00789 | 43 | | | 001-099 | |
| 2536T | 24 | BV | EB | | 3-2 | 31-41-11 | D00319A | C10 | | | | D00789 | 43 | | | 115-199 | |
| 2536W | 24 | BV | FJ | | 0-0 | 31-41-11 | D00319A | C11 | | | | D00789 | 44 | | | 001-099 | |
| 2536W | 24 | BV | EB | | 0-0 | 31-41-11 | D00319A | C11 | | | | D00789 | 44 | | | 115-199 | |
| 2536Z | | | FJ | | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | | D00789 | | | AM | 001-099 | |
| 2536Z | | | EB | | 0-0 | 31-41-11 | GD02217 | ST.. | 2 | | | D00789 | | | AM | 115-199 | |
| 2537T | 24 | BV | FK | | 4-1 | 31-41-11 | D41069J | | 2 | | | D00789 | 3 | | | 001-099 | |
| 2537T | 24 | BV | EC | | 4-0 | 31-41-11 | D41069J | | 2 | | | D00789 | 3 | | | 115-199 | |
| 2537W | 24 | BV | FK | | 0-0 | 31-41-11 | D41069J | | 3 | | | D00789 | 4 | | | 001-099 | |
| 2537W | 24 | BV | EC | | 0-0 | 31-41-11 | D41069J | | 3 | | | D00789 | 4 | | | 115-199 | |
| 2537Z | | | FK | | 0-0 | 31-41-11 | D41069J | | 1 | | | D00789 | | | AD | 001-099 | |
| 2537Z | | | EC | | 0-0 | 31-41-11 | D41069J | | 1 | | | D00789 | | | AD | 115-199 | |
| 2538T | 24 | BV | FL | | 4-1 | 31-41-11 | D41069J | | 5 | | | D00789 | 9 | | | 001-099 | |
| 2538T | 24 | BV | ED | | 4-0 | 31-41-11 | D41069J | | 5 | | | D00789 | 9 | | | 115-199 | |
| 2538W | 24 | BV | FL | | 0-0 | 31-41-11 | D41069J | | 6 | | | D00789 | 10 | | | 001-099 | |
| 2538W | 24 | BV | ED | | 0-0 | 31-41-11 | D41069J | | 6 | | | D00789 | 10 | | | 115-199 | |
| 2538Z | | | FL | | 0-0 | 31-41-11 | D41069J | | 4 | | | D00789 | | | AE | 001-099 | |
| 2538Z | | | ED | | 0-0 | 31-41-11 | D41069J | | 4 | | | D00789 | | | AE | 115-199 | |
| 2539T | 24 | BV | FM | | 4-1 | 31-41-11 | D41069J | | 8 | | | D00789 | 15 | | | 001-099 | |
| 2539T | 24 | BV | EE | | 4-0 | 31-41-11 | D41069J | | 8 | | | D00789 | 15 | | | 115-199 | |
| 2539W | 24 | BV | FM | | 0-0 | 31-41-11 | D41069J | | 9 | | | D00789 | 16 | | | 001-099 | |
| 2539W | 24 | BV | EE | | 0-0 | 31-41-11 | D41069J | | 9 | | | D00789 | 16 | | | 115-199 | |
| 2539Z | | | FM | | 0-0 | 31-41-11 | D41069J | | 7 | | | D00789 | | | AF | 001-099 | |
| 2539Z | | | EE | | 0-0 | 31-41-11 | D41069J | | 7 | | | D00789 | | | AF | 115-199 | |
| 2540T | 24 | BV | FN | | 4-1 | 31-41-11 | D41069J | | 11 | | | D00789 | 21 | | | 001-099 | |
| 2540T | 24 | BV | EF | | 4-0 | 31-41-11 | D41069J | | 11 | | | D00789 | 21 | | | 115-199 | |
| 2540W | 24 | BV | FN | | 0-0 | 31-41-11 | D41069J | | 12 | | | D00789 | 22 | | | 001-099 | |
| 2540W | 24 | BV | EF | | 0-0 | 31-41-11 | D41069J | | 12 | | | D00789 | 22 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 103

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------|-------------|----|-------|-----|------------------------------|----------|---------|------|------|--------|-------|--------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2540Z | | | | FN | 0-0 | 31-41-11 | D41069J | 10 | | | | D00789 | | | AI | 001-099 |
| 2540Z | | | | EF | 0-0 | 31-41-11 | D41069J | 10 | | | | D00789 | | | AI | 115-199 |
| 2541T | 24 | | BV | FO | 4-1 | 31-41-11 | D41069J | 14 | | | | D00789 | 27 | | | 001-099 |
| 2541T | 24 | | BV | EG | 4-0 | 31-41-11 | D41069J | 14 | | | | D00789 | 27 | | | 115-199 |
| 2541W | 24 | | BV | FO | 0-0 | 31-41-11 | D41069J | 15 | | | | D00789 | 28 | | | 001-099 |
| 2541W | 24 | | BV | EG | 0-0 | 31-41-11 | D41069J | 15 | | | | D00789 | 28 | | | 115-199 |
| 2541Z | | | | FO | 0-0 | 31-41-11 | D41069J | 13 | | | | D00789 | | | AJ | 001-099 |
| 2541Z | | | | EG | 0-0 | 31-41-11 | D41069J | 13 | | | | D00789 | | | AJ | 115-199 |
| 2542T | 24 | | BV | FP | 4-1 | 31-41-11 | D41069J | 17 | | | | D00789 | 33 | | | 001-099 |
| 2542T | 24 | | BV | EH | 4-0 | 31-41-11 | D41069J | 17 | | | | D00789 | 33 | | | 115-199 |
| 2542W | 24 | | BV | FP | 0-0 | 31-41-11 | D41069J | 18 | | | | D00789 | 34 | | | 001-099 |
| 2542W | 24 | | BV | EH | 0-0 | 31-41-11 | D41069J | 18 | | | | D00789 | 34 | | | 115-199 |
| 2542Z | | | | FP | 0-0 | 31-41-11 | D41069J | 16 | | | | D00789 | | | AK | 001-099 |
| 2542Z | | | | EH | 0-0 | 31-41-11 | D41069J | 16 | | | | D00789 | | | AK | 115-199 |
| 2543T | 24 | | BV | FQ | 4-1 | 31-41-11 | D41069J | 20 | | | | D00789 | 39 | | | 001-099 |
| 2543T | 24 | | BV | EI | 4-0 | 31-41-11 | D41069J | 20 | | | | D00789 | 39 | | | 115-199 |
| 2543W | 24 | | BV | FQ | 0-0 | 31-41-11 | D41069J | 21 | | | | D00789 | 40 | | | 001-099 |
| 2543W | 24 | | BV | EI | 0-0 | 31-41-11 | D41069J | 21 | | | | D00789 | 40 | | | 115-199 |
| 2543Z | | | | FQ | 0-0 | 31-41-11 | D41069J | 19 | | | | D00789 | | | AL | 001-099 |
| 2543Z | | | | EI | 0-0 | 31-41-11 | D41069J | 19 | | | | D00789 | | | AL | 115-199 |
| 2544T | 24 | | BV | FR | 4-1 | 31-41-11 | D41069J | 23 | | | | D00789 | 45 | | | 001-099 |
| 2544T | 24 | | BV | EJ | 4-0 | 31-41-11 | D41069J | 23 | | | | D00789 | 45 | | | 115-199 |
| 2544W | 24 | | BV | FR | 0-0 | 31-41-11 | D41069J | 24 | | | | D00789 | 46 | | | 001-099 |
| 2544W | 24 | | BV | EJ | 0-0 | 31-41-11 | D41069J | 24 | | | | D00789 | 46 | | | 115-199 |
| 2544Z | | | | FR | 0-0 | 31-41-11 | D41069J | 22 | | | | D00789 | | | AM | 001-099 |
| 2544Z | | | | EJ | 0-0 | 31-41-11 | D41069J | 22 | | | | D00789 | | | AM | 115-199 |
| 2554T | 24 | | BV | GB | 3-2 | 31-41-21 | D00321A | B12 | | | | D00791 | 59 | | | 001-099 |
| 2554T | 24 | | BV | FA | 3-2 | 31-41-21 | D00321A | B12 | | | | D00791 | 59 | | | 115-199 |
| 2554W | 24 | | BV | GB | 0-0 | 31-41-21 | D00321A | A12 | | | | D00791 | 60 | | | 001-099 |
| 2554W | 24 | | BV | FA | 0-0 | 31-41-21 | D00321A | A12 | | | | D00791 | 60 | | | 115-199 |
| 2554Z | | | | GB | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | | D00791 | | | BA | 001-099 |
| 2554Z | | | | FA | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | | D00791 | | | BA | 115-199 |
| 2555T | 24 | | BV | GC | 3-2 | 31-41-21 | D00321A | B14 | | | | D00791 | 65 | | | 001-099 |
| 2555T | 24 | | BV | FB | 3-2 | 31-41-21 | D00321A | B14 | | | | D00791 | 65 | | | 115-199 |
| 2555W | 24 | | BV | GC | 0-0 | 31-41-21 | D00321A | A14 | | | | D00791 | 66 | | | 001-099 |
| 2555W | 24 | | BV | FB | 0-0 | 31-41-21 | D00321A | A14 | | | | D00791 | 66 | | | 115-199 |
| 2555Z | | | | GC | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | | D00791 | | | BB | 001-099 |
| 2555Z | | | | FB | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | | D00791 | | | BB | 115-199 |
| 2556T | 24 | | BV | GD | 3-2 | 31-41-21 | D00321A | B13 | | | | D00791 | 71 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 104

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2556T | 24 | BV | FC | | 3-2 | 31-41-21 | D00321A | B13 | | | D00791 | 71 | | | 115-199 |
| 2556W | 24 | BV | GD | | 0-0 | 31-41-21 | D00321A | A13 | | | D00791 | 72 | | | 001-099 |
| 2556W | 24 | BV | FC | | 0-0 | 31-41-21 | D00321A | A13 | | | D00791 | 72 | | | 115-199 |
| 2556Z | | | GD | | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | D00791 | | | BC | 001-099 |
| 2556Z | | | FC | | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | D00791 | | | BC | 115-199 |
| 2557T | 24 | BV | GE | | 3-2 | 31-41-21 | D00321A | B15 | | | D00791 | 77 | | | 001-099 |
| 2557T | 24 | BV | FD | | 3-2 | 31-41-21 | D00321A | B15 | | | D00791 | 77 | | | 115-199 |
| 2557W | 24 | BV | GE | | 0-0 | 31-41-21 | D00321A | A15 | | | D00791 | 78 | | | 001-099 |
| 2557W | 24 | BV | FD | | 0-0 | 31-41-21 | D00321A | A15 | | | D00791 | 78 | | | 115-199 |
| 2557Z | | | GE | | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | D00791 | | | BD | 001-099 |
| 2557Z | | | FD | | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | D00791 | | | BD | 115-199 |
| 2558T | 24 | BV | GF | | 3-2 | 31-41-21 | D00321A | A01 | | | D00791 | 83 | | | 001-099 |
| 2558T | 24 | BV | FE | | 3-2 | 31-41-21 | D00321A | A01 | | | D00791 | 83 | | | 115-199 |
| 2558W | 24 | BV | GF | | 0-0 | 31-41-21 | D00321A | A02 | | | D00791 | 84 | | | 001-099 |
| 2558W | 24 | BV | FE | | 0-0 | 31-41-21 | D00321A | A02 | | | D00791 | 84 | | | 115-199 |
| 2558Z | | | GF | | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | D00791 | | | BE | 001-099 |
| 2558Z | | | FE | | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | D00791 | | | BE | 115-199 |
| 2559T | 24 | BV | GG | | 3-1 | 31-41-21 | D00321B | A03 | | | D00791 | 89 | | | 001-099 |
| 2559T | 24 | BV | FF | | 3-1 | 31-41-21 | D00321B | A03 | | | D00791 | 89 | | | 115-199 |
| 2559W | 24 | BV | GG | | 0-0 | 31-41-21 | D00321B | B03 | | | D00791 | 90 | | | 001-099 |
| 2559W | 24 | BV | FF | | 0-0 | 31-41-21 | D00321B | B03 | | | D00791 | 90 | | | 115-199 |
| 2559Z | | | GG | | 0-0 | 31-41-21 | GD02220 | ST.. | 2 | | D00791 | | | BF | 001-099 |
| 2559Z | | | FF | | 0-0 | 31-41-21 | GD02220 | ST.. | 2 | | D00791 | | | BF | 115-199 |
| 2560T | 24 | BV | GH | | 3-1 | 31-41-21 | D00321B | B04 | | | D00791 | 95 | | | 001-099 |
| 2560T | 24 | BV | FG | | 3-1 | 31-41-21 | D00321B | B04 | | | D00791 | 95 | | | 115-199 |
| 2560W | 24 | BV | GH | | 0-0 | 31-41-21 | D00321B | A04 | | | D00791 | 96 | | | 001-099 |
| 2560W | 24 | BV | FG | | 0-0 | 31-41-21 | D00321B | A04 | | | D00791 | 96 | | | 115-199 |
| 2560Z | | | GH | | 0-0 | 31-41-21 | GD02220 | ST.. | 2 | | D00791 | | | BG | 001-099 |
| 2560Z | | | FG | | 0-0 | 31-41-21 | GD02220 | ST.. | 2 | | D00791 | | | BG | 115-199 |
| 2561T | 24 | BV | GI | | 3-2 | 31-41-21 | D00321A | B11 | | | D00791 | 101 | | | 001-099 |
| 2561T | 24 | BV | FH | | 3-2 | 31-41-21 | D00321A | B11 | | | D00791 | 101 | | | 115-199 |
| 2561W | 24 | BV | GI | | 0-0 | 31-41-21 | D00321A | A11 | | | D00791 | 102 | | | 001-099 |
| 2561W | 24 | BV | FH | | 0-0 | 31-41-21 | D00321A | A11 | | | D00791 | 102 | | | 115-199 |
| 2561Z | | | GI | | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | D00791 | | | BH | 001-099 |
| 2561Z | | | FH | | 0-0 | 31-41-21 | GD02219 | ST.. | 2 | | D00791 | | | BH | 115-199 |
| 2562T | 24 | BV | GJ | | 3-1 | 31-41-21 | D41071J | | 2 | | D00791 | 3 | | | 001-099 |
| 2562T | 24 | BV | FI | | 3-2 | 31-41-21 | D41071J | | 2 | | D00791 | 3 | | | 115-199 |
| 2562W | 24 | BV | GJ | | 0-0 | 31-41-21 | D41071J | | 3 | | D00791 | 4 | | | 001-099 |
| 2562W | 24 | BV | FI | | 0-0 | 31-41-21 | D41071J | | 3 | | D00791 | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 105

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------------|---------|------|------|--------|--------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | |
| 2562Z | | | | GJ | 0-0 | 31-41-21 | D41071J | | 1 | | D00791 | | | BA | 001-099 |
| 2562Z | | | | FI | 0-0 | 31-41-21 | D41071J | | 1 | | D00791 | | | BA | 115-199 |
| 2563T | | 24 | BV | GK | 3-1 | 31-41-21 | D41071J | | 5 | | D00791 | 9 | | | 001-099 |
| 2563T | | 24 | BV | FJ | 3-2 | 31-41-21 | D41071J | | 5 | | D00791 | 9 | | | 115-199 |
| 2563W | | 24 | BV | GK | 0-0 | 31-41-21 | D41071J | | 6 | | D00791 | 10 | | | 001-099 |
| 2563W | | 24 | BV | FJ | 0-0 | 31-41-21 | D41071J | | 6 | | D00791 | 10 | | | 115-199 |
| 2563Z | | | | GK | 0-0 | 31-41-21 | D41071J | | 4 | | D00791 | | | BB | 001-099 |
| 2563Z | | | | FJ | 0-0 | 31-41-21 | D41071J | | 4 | | D00791 | | | BB | 115-199 |
| 2564T | | 24 | BV | GL | 3-1 | 31-41-21 | D41071J | | 8 | | D00791 | 15 | | | 001-099 |
| 2564T | | 24 | BV | FK | 3-2 | 31-41-21 | D41071J | | 8 | | D00791 | 15 | | | 115-199 |
| 2564W | | 24 | BV | GL | 0-0 | 31-41-21 | D41071J | | 9 | | D00791 | 16 | | | 001-099 |
| 2564W | | 24 | BV | FK | 0-0 | 31-41-21 | D41071J | | 9 | | D00791 | 16 | | | 115-199 |
| 2564Z | | | | GL | 0-0 | 31-41-21 | D41071J | | 7 | | D00791 | | | BC | 001-099 |
| 2564Z | | | | FK | 0-0 | 31-41-21 | D41071J | | 7 | | D00791 | | | BC | 115-199 |
| 2565T | | 24 | BV | GM | 3-1 | 31-41-21 | D41071J | | 11 | | D00791 | 21 | | | 001-099 |
| 2565T | | 24 | BV | FL | 3-2 | 31-41-21 | D41071J | | 11 | | D00791 | 21 | | | 115-199 |
| 2565W | | 24 | BV | GM | 0-0 | 31-41-21 | D41071J | | 12 | | D00791 | 22 | | | 001-099 |
| 2565W | | 24 | BV | FL | 0-0 | 31-41-21 | D41071J | | 12 | | D00791 | 22 | | | 115-199 |
| 2565Z | | | | GM | 0-0 | 31-41-21 | D41071J | | 10 | | D00791 | | | BD | 001-099 |
| 2565Z | | | | FL | 0-0 | 31-41-21 | D41071J | | 10 | | D00791 | | | BD | 115-199 |
| 2566T | | 24 | BV | GN | 3-1 | 31-41-21 | D41071J | | 14 | | D00791 | 27 | | | 001-099 |
| 2566T | | 24 | BV | FM | 3-2 | 31-41-21 | D41071J | | 14 | | D00791 | 27 | | | 115-199 |
| 2566W | | 24 | BV | GN | 0-0 | 31-41-21 | D41071J | | 15 | | D00791 | 28 | | | 001-099 |
| 2566W | | 24 | BV | FM | 0-0 | 31-41-21 | D41071J | | 15 | | D00791 | 28 | | | 115-199 |
| 2566Z | | | | GN | 0-0 | 31-41-21 | D41071J | | 13 | | D00791 | | | BE | 001-099 |
| 2566Z | | | | FM | 0-0 | 31-41-21 | D41071J | | 13 | | D00791 | | | BE | 115-199 |
| 2567T | | 24 | BV | GO | 3-1 | 31-41-21 | D41071J | | 17 | | D00791 | 33 | | | 001-099 |
| 2567T | | 24 | BV | FN | 3-2 | 31-41-21 | D41071J | | 17 | | D00791 | 33 | | | 115-199 |
| 2567W | | 24 | BV | GO | 0-0 | 31-41-21 | D41071J | | 18 | | D00791 | 34 | | | 001-099 |
| 2567W | | 24 | BV | FN | 0-0 | 31-41-21 | D41071J | | 18 | | D00791 | 34 | | | 115-199 |
| 2567Z | | | | GO | 0-0 | 31-41-21 | D41071J | | 16 | | D00791 | | | BF | 001-099 |
| 2567Z | | | | FN | 0-0 | 31-41-21 | D41071J | | 16 | | D00791 | | | BF | 115-199 |
| 2568T | | 24 | BV | GP | 3-1 | 31-41-21 | D41071J | | 20 | | D00791 | 39 | | | 001-099 |
| 2568T | | 24 | BV | FO | 3-2 | 31-41-21 | D41071J | | 20 | | D00791 | 39 | | | 115-199 |
| 2568W | | 24 | BV | GP | 0-0 | 31-41-21 | D41071J | | 21 | | D00791 | 40 | | | 001-099 |
| 2568W | | 24 | BV | FO | 0-0 | 31-41-21 | D41071J | | 21 | | D00791 | 40 | | | 115-199 |
| 2568Z | | | | GP | 0-0 | 31-41-21 | D41071J | | 19 | | D00791 | | | BG | 001-099 |
| 2568Z | | | | FO | 0-0 | 31-41-21 | D41071J | | 19 | | D00791 | | | BG | 115-199 |
| 2569T | | 24 | BV | GQ | 3-1 | 31-41-21 | D41071J | | 23 | | D00791 | 45 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 106

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2569T | 24 | BV | FP | | 3-2 | 31-41-21 | D41071J | 23 | | | D00791 | 45 | | | 115-199 |
| 2569W | 24 | BV | GQ | | 0-0 | 31-41-21 | D41071J | 24 | | | D00791 | 46 | | | 001-099 |
| 2569W | 24 | BV | FP | | 0-0 | 31-41-21 | D41071J | 24 | | | D00791 | 46 | | | 115-199 |
| 2569Z | | | GQ | | 0-0 | 31-41-21 | D41071J | 22 | | | D00791 | | BH | | 001-099 |
| 2569Z | | | FP | | 0-0 | 31-41-21 | D41071J | 22 | | | D00791 | | BH | | 115-199 |
| 2570T | 24 | BV | GR | | 3-2 | 31-41-11 | D00321A | C12 | | | D00789 | 59 | | | 001-099 |
| 2570T | 24 | BV | HB | | 3-2 | 31-41-11 | D00321A | C12 | | | D00789 | 59 | | | 115-199 |
| 2570W | 24 | BV | GR | | 0-0 | 31-41-11 | D00321A | C13 | | | D00789 | 60 | | | 001-099 |
| 2570W | 24 | BV | HB | | 0-0 | 31-41-11 | D00321A | C13 | | | D00789 | 60 | | | 115-199 |
| 2570Z | | | GR | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AD | | 001-099 |
| 2570Z | | | HB | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AD | | 115-199 |
| 2571T | 24 | BV | GS | | 3-2 | 31-41-11 | D00321A | B04 | | | D00789 | 65 | | | 001-099 |
| 2571T | 24 | BV | HQ | | 3-2 | 31-41-11 | D00321A | B04 | | | D00789 | 65 | | | 115-199 |
| 2571W | 24 | BV | GS | | 0-0 | 31-41-11 | D00321A | A04 | | | D00789 | 66 | | | 001-099 |
| 2571W | 24 | BV | HQ | | 0-0 | 31-41-11 | D00321A | A04 | | | D00789 | 66 | | | 115-199 |
| 2571Z | | | GS | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AE | | 001-099 |
| 2571Z | | | HQ | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AE | | 115-199 |
| 2572T | 24 | BV | GT | | 3-2 | 31-41-11 | D00321A | C14 | | | D00789 | 71 | | | 001-099 |
| 2572T | 24 | BV | HD | | 3-2 | 31-41-11 | D00321A | C14 | | | D00789 | 71 | | | 115-199 |
| 2572W | 24 | BV | GT | | 0-0 | 31-41-11 | D00321A | C15 | | | D00789 | 72 | | | 001-099 |
| 2572W | 24 | BV | HD | | 0-0 | 31-41-11 | D00321A | C15 | | | D00789 | 72 | | | 115-199 |
| 2572Z | | | GT | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AF | | 001-099 |
| 2572Z | | | HD | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AF | | 115-199 |
| 2573T | 24 | BV | GU | | 3-2 | 31-41-11 | D00321A | B05 | | | D00789 | 77 | | | 001-099 |
| 2573T | 24 | BV | HE | | 3-2 | 31-41-11 | D00321A | B05 | | | D00789 | 77 | | | 115-199 |
| 2573W | 24 | BV | GU | | 0-0 | 31-41-11 | D00321A | A05 | | | D00789 | 78 | | | 001-099 |
| 2573W | 24 | BV | HE | | 0-0 | 31-41-11 | D00321A | A05 | | | D00789 | 78 | | | 115-199 |
| 2573Z | | | GU | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AI | | 001-099 |
| 2573Z | | | HE | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AI | | 115-199 |
| 2574T | 24 | BV | GV | | 3-2 | 31-41-11 | D00321A | C01 | | | D00789 | 83 | | | 001-099 |
| 2574T | 24 | BV | HF | | 3-2 | 31-41-11 | D00321A | C01 | | | D00789 | 83 | | | 115-199 |
| 2574W | 24 | BV | GV | | 0-0 | 31-41-11 | D00321A | C02 | | | D00789 | 84 | | | 001-099 |
| 2574W | 24 | BV | HF | | 0-0 | 31-41-11 | D00321A | C02 | | | D00789 | 84 | | | 115-199 |
| 2574Z | | | GV | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AJ | | 001-099 |
| 2574Z | | | HF | | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | | D00789 | | AJ | | 115-199 |
| 2575T | 24 | BV | GW | | 3-1 | 31-41-11 | D00321B | A01 | | | D00789 | 89 | | | 001-099 |
| 2575T | 24 | BV | HG | | 3-1 | 31-41-11 | D00321B | A01 | | | D00789 | 89 | | | 115-199 |
| 2575W | 24 | BV | GW | | 0-0 | 31-41-11 | D00321B | B01 | | | D00789 | 90 | | | 001-099 |
| 2575W | 24 | BV | HG | | 0-0 | 31-41-11 | D00321B | B01 | | | D00789 | 90 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 107

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|-------------------------------------|-------|---------|----------|---------|------|--------|--------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1275 | 286N1275 | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | | |
| 2575Z | | | GW | 0-0 | 31-41-11 | GD02220 | ST.. | 2 | D00789 | | | AK | 001-099 | | |
| 2575Z | | | HG | 0-0 | 31-41-11 | GD02220 | ST.. | 2 | D00789 | | | AK | 115-199 | | |
| 2576T | 24 | BV | GX | 3-1 | 31-41-11 | D00321B | A02 | | D00789 | 95 | | | 001-099 | | |
| 2576T | 24 | BV | HH | 3-1 | 31-41-11 | D00321B | A02 | | D00789 | 95 | | | 115-199 | | |
| 2576W | 24 | BV | GX | 0-0 | 31-41-11 | D00321B | B02 | | D00789 | 96 | | | 001-099 | | |
| 2576W | 24 | BV | HH | 0-0 | 31-41-11 | D00321B | B02 | | D00789 | 96 | | | 115-199 | | |
| 2576Z | | | GX | 0-0 | 31-41-11 | GD02220 | ST.. | 2 | D00789 | | | AL | 001-099 | | |
| 2576Z | | | HH | 0-0 | 31-41-11 | GD02220 | ST.. | 2 | D00789 | | | AL | 115-199 | | |
| 2577T | 24 | BV | GY | 3-2 | 31-41-11 | D00321A | C10 | | D00789 | 101 | | | 001-099 | | |
| 2577T | 24 | BV | HI | 3-2 | 31-41-11 | D00321A | C10 | | D00789 | 101 | | | 115-199 | | |
| 2577W | 24 | BV | GY | 0-0 | 31-41-11 | D00321A | C11 | | D00789 | 102 | | | 001-099 | | |
| 2577W | 24 | BV | HI | 0-0 | 31-41-11 | D00321A | C11 | | D00789 | 102 | | | 115-199 | | |
| 2577Z | | | GY | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | D00789 | | | AM | 001-099 | | |
| 2577Z | | | HI | 0-0 | 31-41-11 | GD02219 | ST.. | 2 | D00789 | | | AM | 115-199 | | |
| 2578T | 24 | BV | GZ | 3-1 | 31-41-21 | D00319A | B12 | | D00791 | 1 | | | 001-099 | | |
| 2578T | 24 | BV | HJ | 3-2 | 31-41-21 | D00319A | B12 | | D00791 | 1 | | | 115-199 | | |
| 2578W | 24 | BV | GZ | 0-0 | 31-41-21 | D00319A | A12 | | D00791 | 2 | | | 001-099 | | |
| 2578W | 24 | BV | HJ | 0-0 | 31-41-21 | D00319A | A12 | | D00791 | 2 | | | 115-199 | | |
| 2578Z | | | GZ | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | D00791 | | | BA | 001-099 | | |
| 2578Z | | | HJ | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | D00791 | | | BA | 115-199 | | |
| 2579T | 24 | BV | HA | 3-1 | 31-41-21 | D00319A | B14 | | D00791 | 7 | | | 001-099 | | |
| 2579T | 24 | BV | HK | 3-2 | 31-41-21 | D00319A | B14 | | D00791 | 7 | | | 115-199 | | |
| 2579W | 24 | BV | HA | 0-0 | 31-41-21 | D00319A | A14 | | D00791 | 8 | | | 001-099 | | |
| 2579W | 24 | BV | HK | 0-0 | 31-41-21 | D00319A | A14 | | D00791 | 8 | | | 115-199 | | |
| 2579Z | | | HA | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | D00791 | | | BB | 001-099 | | |
| 2579Z | | | HK | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | D00791 | | | BB | 115-199 | | |
| 2580T | 24 | BV | HB | 3-1 | 31-41-21 | D00319A | B13 | | D00791 | 13 | | | 001-099 | | |
| 2580T | 24 | BV | HL | 3-2 | 31-41-21 | D00319A | B13 | | D00791 | 13 | | | 115-199 | | |
| 2580W | 24 | BV | HB | 0-0 | 31-41-21 | D00319A | A13 | | D00791 | 14 | | | 001-099 | | |
| 2580W | 24 | BV | HL | 0-0 | 31-41-21 | D00319A | A13 | | D00791 | 14 | | | 115-199 | | |
| 2580Z | | | HB | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | D00791 | | | BC | 001-099 | | |
| 2580Z | | | HL | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | D00791 | | | BC | 115-199 | | |
| 2581T | 24 | BV | HC | 3-1 | 31-41-21 | D00319A | B15 | | D00791 | 19 | | | 001-099 | | |
| 2581T | 24 | BV | HM | 3-2 | 31-41-21 | D00319A | B15 | | D00791 | 19 | | | 115-199 | | |
| 2581W | 24 | BV | HC | 0-0 | 31-41-21 | D00319A | A15 | | D00791 | 20 | | | 001-099 | | |
| 2581W | 24 | BV | HM | 0-0 | 31-41-21 | D00319A | A15 | | D00791 | 20 | | | 115-199 | | |
| 2581Z | | | HC | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | D00791 | | | BD | 001-099 | | |
| 2581Z | | | HM | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | D00791 | | | BD | 115-199 | | |
| 2582T | 24 | BV | HD | 3-1 | 31-41-21 | D00319A | A01 | | D00791 | 25 | | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 108

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2582T | 24 | BV | HN | | 3-2 | 31-41-21 | D00319A | A01 | | | D00791 | 25 | | | 115-199 |
| 2582W | 24 | BV | HD | | 0-0 | 31-41-21 | D00319A | A02 | | | D00791 | 26 | | | 001-099 |
| 2582W | 24 | BV | HN | | 0-0 | 31-41-21 | D00319A | A02 | | | D00791 | 26 | | | 115-199 |
| 2582Z | | | HD | | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | | D00791 | | | BE | 001-099 |
| 2582Z | | | HN | | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | | D00791 | | | BE | 115-199 |
| 2583T | 24 | BV | HE | | 3-0 | 31-41-21 | D00319B | A03 | | | D00791 | 31 | | | 001-099 |
| 2583T | 24 | BV | HO | | 3-1 | 31-41-21 | D00319B | A03 | | | D00791 | 31 | | | 115-199 |
| 2583W | 24 | BV | HE | | 0-0 | 31-41-21 | D00319B | B03 | | | D00791 | 32 | | | 001-099 |
| 2583W | 24 | BV | HO | | 0-0 | 31-41-21 | D00319B | B03 | | | D00791 | 32 | | | 115-199 |
| 2583Z | | | HE | | 0-0 | 31-41-21 | GD02218 | ST.. | 2 | | D00791 | | | BF | 001-099 |
| 2583Z | | | HO | | 0-0 | 31-41-21 | GD02218 | ST.. | 2 | | D00791 | | | BF | 115-199 |
| 2584T | 24 | BV | HF | | 3-0 | 31-41-21 | D00319B | B04 | | | D00791 | 37 | | | 001-099 |
| 2584T | 24 | BV | HP | | 3-1 | 31-41-21 | D00319B | B04 | | | D00791 | 37 | | | 115-199 |
| 2584W | 24 | BV | HF | | 0-0 | 31-41-21 | D00319B | A04 | | | D00791 | 38 | | | 001-099 |
| 2584W | 24 | BV | HP | | 0-0 | 31-41-21 | D00319B | A04 | | | D00791 | 38 | | | 115-199 |
| 2584Z | | | HF | | 0-0 | 31-41-21 | GD02218 | ST.. | 2 | | D00791 | | | BG | 001-099 |
| 2584Z | | | HP | | 0-0 | 31-41-21 | GD02218 | ST.. | 2 | | D00791 | | | BG | 115-199 |
| 2585T | 24 | BV | HG | | 3-1 | 31-41-21 | D00319A | B11 | | | D00791 | 43 | | | 001-099 |
| 2585T | 24 | BV | HX | | 3-2 | 31-41-21 | D00319A | B11 | | | D00791 | 43 | | | 115-199 |
| 2585W | 24 | BV | HG | | 0-0 | 31-41-21 | D00319A | A11 | | | D00791 | 44 | | | 001-099 |
| 2585W | 24 | BV | HX | | 0-0 | 31-41-21 | D00319A | A11 | | | D00791 | 44 | | | 115-199 |
| 2585Z | | | HG | | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | | D00791 | | | BH | 001-099 |
| 2585Z | | | HX | | 0-0 | 31-41-21 | GD02217 | ST.. | 2 | | D00791 | | | BH | 115-199 |
| 2590B | 24 | G2 | HL | | 4-1 | 77-12-31 | D41736J | | 29 | | TB0207Z | 9 | BJ | | 001, 003-099 |
| 2590B | 24 | G2 | HL | | 4-2 | 77-12-31 | D41736J | | 29 | | TB0207Z | 9 | BJ | | 002 |
| 2590B | 24 | G2 | NA | | 4-0 | 77-12-31 | D41736J | | 29 | | TB0207Z | 9 | BJ | | 115-199 |
| 2590R | 24 | G2 | HL | | 0-0 | 77-12-31 | D41736J | | 28 | | TB0207Z | 10 | BJ | | 001-099 |
| 2590R | 24 | G2 | NA | | 0-0 | 77-12-31 | D41736J | | 28 | | TB0207Z | 10 | BJ | | 115-199 |
| 2590Z | | | HL | | 0-0 | 77-12-31 | D41736J | | 30 | | TB0207Z | | | TE | 001-099 |
| 2590Z | | | NA | | 0-0 | 77-12-31 | D41736J | | 30 | | TB0207Z | | | JF | 115-199 |
| 2592B | 24 | G2 | HN | | 3-11 | 77-12-31 | D41734J | | 38 | | TB0207Z | 16 | BJ | | 001-099 |
| 2592B | 24 | G2 | NB | | 3-9 | 77-12-31 | D41734J | | 38 | | TB0207Z | 16 | BJ | | 115-199 |
| 2592R | 24 | G2 | HN | | 0-0 | 77-12-31 | D41734J | | 37 | | TB0207Z | 15 | BJ | | 001-099 |
| 2592R | 24 | G2 | NB | | 0-0 | 77-12-31 | D41734J | | 37 | | TB0207Z | 15 | BJ | | 115-199 |
| 2592Z | | | HN | | 0-0 | 77-12-31 | D41734J | | 39 | | TB0207Z | | | TC | 001-099 |
| 2592Z | | | NB | | 0-0 | 77-12-31 | D41734J | | 39 | | TB0207Z | | | JE | 115-199 |
| 2611B | 24 | G2 | IG | | 2-10 | 73-21-22 | D41776J | | 14 | | D42185J | 19 | | | 001-099 |
| 2611B | 24 | G2 | PA | | 2-11 | 73-21-22 | D41776J | | 14 | | D42185J | 19 | | | 115-199 |
| 2611R | 24 | G2 | IG | | 0-0 | 73-21-22 | D41776J | | 13 | | D42185J | 20 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 109

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2611R | 24 | G2 | PA | | 0-0 | 73-21-22 | D41776J | 13 | | | D42185J | 20 | | | 115-199 |
| 2611Z | | | IG | | 0-0 | 73-21-22 | D41776J | | | RS | D42185J | | | RT | 001-099 |
| 2611Z | | | PA | | 0-0 | 73-21-22 | D41776J | | | KB | D42185J | | | KA | 115-199 |
| 2612B | 24 | G2 | IH | | 2-10 | 73-21-22 | D41776J | 16 | | | D42185J | 16 | | | 001-099 |
| 2612B | 24 | G2 | PB | | 2-11 | 73-21-22 | D41776J | 16 | | | D42185J | 16 | | | 115-199 |
| 2612R | 24 | G2 | IH | | 0-0 | 73-21-22 | D41776J | 15 | | | D42185J | 17 | | | 001-099 |
| 2612R | 24 | G2 | PB | | 0-0 | 73-21-22 | D41776J | 15 | | | D42185J | 17 | | | 115-199 |
| 2612Z | | | IH | | 0-0 | 73-21-22 | D41776J | | | RS | D42185J | | | RT | 001-099 |
| 2612Z | | | PB | | 0-0 | 73-21-22 | D41776J | | | KB | D42185J | | | KA | 115-199 |
| 2613B | 24 | G2 | II | | 2-4 | 77-12-11 | D41738J | 40 | | | TB0207Z | 112 | BJ | | 001, 003-099 |
| 2613B | 24 | G2 | II | | 2-5 | 77-12-11 | D41738J | 40 | | | TB0207Z | 112 | BJ | | 002 |
| 2613B | 24 | G2 | GY | | 2-6 | 77-12-11 | D41738J | 40 | | | TB0207Z | 112 | BJ | | 115-199 |
| 2613R | 24 | G2 | II | | 0-0 | 77-12-11 | D41738J | 39 | | | TB0207Z | 111 | BJ | | 001-099 |
| 2613R | 24 | G2 | GY | | 0-0 | 77-12-11 | D41738J | 39 | | | TB0207Z | 111 | BJ | | 115-199 |
| 2613Z | | | II | | 0-0 | 77-12-11 | D41738J | 41 | | | TB0207Z | | | RN | 001-099 |
| 2613Z | | | GY | | 0-0 | 77-12-11 | D41738J | 41 | | | TB0207Z | | | SB | 115-199 |
| 2614B | 24 | G2 | IJ | | 3-3 | 77-12-11 | D41776J | 37 | | | TB0207Z | 107 | BJ | | 001-099 |
| 2614B | 24 | G2 | HA | | 3-3 | 77-12-11 | D41776J | 37 | | | TB0207Z | 107 | BJ | | 115-199 |
| 2614R | 24 | G2 | IJ | | 0-0 | 77-12-11 | D41776J | 38 | | | TB0207Z | 106 | BJ | | 001-099 |
| 2614R | 24 | G2 | HA | | 0-0 | 77-12-11 | D41776J | 38 | | | TB0207Z | 106 | BJ | | 115-199 |
| 2614Z | | | IJ | | 0-0 | 77-12-11 | D41776J | 39 | | | TB0207Z | | | RU | 001-099 |
| 2614Z | | | HA | | 0-0 | 77-12-11 | D41776J | 39 | | | TB0207Z | | | SA | 115-199 |
| 2615B | 24 | G2 | IK | | 4-5 | 77-12-11 | D04240A | A08 | | | TB0207Z | 112 | BJ | | 001, 003-099 |
| 2615B | 24 | G2 | IK | | 4-6 | 77-12-11 | D04240A | A08 | | | TB0207Z | 112 | BJ | | 002 |
| 2615B | 24 | G2 | IE | | 4-5 | 77-12-11 | D04240A | A08 | | | TB0207Z | 112 | BJ | | 115-199 |
| 2615R | 24 | G2 | IK | | 0-0 | 77-12-11 | D04240A | B08 | | | TB0207Z | 111 | BJ | | 001-099 |
| 2615R | 24 | G2 | IE | | 0-0 | 77-12-11 | D04240A | B08 | | | TB0207Z | 111 | BJ | | 115-199 |
| 2615Z | | | IK | | 0-0 | 77-12-11 | D04240A | DED | | | TB0207Z | | | RN | 001-099 |
| 2615Z | | | IE | | 0-0 | 77-12-11 | D04240A | DED | | | TB0207Z | | | SB | 115-199 |
| 2616B | 24 | G2 | IL | | 4-9 | 77-12-11 | D05602B | A08 | | | TB0207Z | 107 | BJ | | 001, 003-099 |
| 2616B | 24 | G2 | IL | | 4-10 | 77-12-11 | D05602B | A08 | | | TB0207Z | 107 | BJ | | 002 |
| 2616B | 24 | G2 | IG | | 4-10 | 77-12-11 | D05602B | A08 | | | TB0207Z | 107 | BJ | | 115-199 |
| 2616R | 24 | G2 | IL | | 0-0 | 77-12-11 | D05602B | B08 | | | TB0207Z | 106 | BJ | | 001-099 |
| 2616R | 24 | G2 | IG | | 0-0 | 77-12-11 | D05602B | B08 | | | TB0207Z | 106 | BJ | | 115-199 |
| 2616Z | | | IL | | 0-0 | 77-12-11 | D05602B | DED | | | TB0207Z | | | RU | 001-099 |
| 2616Z | | | IG | | 0-0 | 77-12-11 | D05602B | DED | | | TB0207Z | | | SA | 115-199 |
| 2617B | 24 | G2 | IM | | 2-4 | 77-12-21 | D05602B | C10 | | | TB0207Y | A007 | BJ | | 001, 003-099 |
| 2617B | 24 | G2 | IM | | 2-5 | 77-12-21 | D05602B | C10 | | | TB0207Y | A007 | BJ | | 002 |
| 2617B | 24 | G2 | IM | | 2-3 | 77-12-21 | D05602B | C10 | | | TB0207Y | A007 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 110

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1270
Page 111
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 2626R | 24 | G2 | IV | | 0-0 | 79-34-11 | D00319D | H09 | | | D41736J | 42 | | | 001-099 |
| 2626R | 24 | G2 | RB | | 0-0 | 79-34-11 | D00319D | H09 | | | D41736J | 42 | | | 115-199 |
| 2626Z | | | IV | | 0-0 | 79-34-11 | D00319D | DED | | | D41736J | | | RB | 001-099 |
| 2626Z | | | RB | | 0-0 | 79-34-11 | D00319D | DED | | | D41736J | | | RB | 115-199 |
| 2627B | 24 | G2 | IW | | 3-7 | 23-41-11 | D41660J | 26 | | | D41867J | 6 | | | 001-099 |
| 2627R | 24 | G2 | IW | | 0-0 | 23-41-11 | D41660J | 27 | | | D41867J | 7 | | | 001-099 |
| 2627Z | | | IW | | 0-0 | 23-41-11 | D41660J | 22 | | | D41867J | 9 | | | 001-099 |
| 3001B | 24 | GM | NA | | 3-8 | 73-31-11 | D41736J | 3 | | | TB0207Y | C034 | BJ | | 001-099 |
| 3001B | 24 | GM | AG | | 3-7 | 73-31-11 | D41736J | 3 | | | TB0207Y | C034 | BJ | | 115-199 |
| 3001R | 24 | GM | NA | | 0-0 | 73-31-11 | D41736J | 2 | | | TB0207Y | A034 | BJ | | 001-099 |
| 3001R | 24 | GM | AG | | 0-0 | 73-31-11 | D41736J | 2 | | | TB0207Y | A034 | BJ | | 115-199 |
| 3001Y | 24 | GM | NA | | 0-0 | 73-31-11 | D41736J | 4 | | | TB0207Y | A035 | BJ | | 001-099 |
| 3001Y | 24 | GM | AG | | 0-0 | 73-31-11 | D41736J | 4 | | | TB0207Y | A035 | BJ | | 115-199 |
| 3002B | 24 | GM | NB | | 4-6 | 73-31-11 | D00321D | K01 | | | TB0207Y | C034 | BJ | | 001-099 |
| 3002B | 24 | GM | AH | | 4-5 | 73-31-11 | D00321D | K01 | | | TB0207Y | C034 | BJ | | 115-199 |
| 3002R | 24 | GM | NB | | 0-0 | 73-31-11 | D00321D | J01 | | | TB0207Y | A034 | BJ | | 001-099 |
| 3002R | 24 | GM | AH | | 0-0 | 73-31-11 | D00321D | J01 | | | TB0207Y | A034 | BJ | | 115-199 |
| 3002Y | 24 | GM | NB | | 0-0 | 73-31-11 | D00321D | H01 | | | TB0207Y | A035 | BJ | | 001-099 |
| 3002Y | 24 | GM | AH | | 0-0 | 73-31-11 | D00321D | H01 | | | TB0207Y | A035 | BJ | | 115-199 |
| 3003B | 24 | GM | NC | | 3-1 | 73-31-11 | D00319D | K01 | | | TB0207Y | C034 | BJ | | 001-099 |
| 3003B | 24 | GM | AI | | 3-1 | 73-31-11 | D00319D | K01 | | | TB0207Y | C034 | BJ | | 115-199 |
| 3003R | 24 | GM | NC | | 0-0 | 73-31-11 | D00319D | J01 | | | TB0207Y | A034 | BJ | | 001-099 |
| 3003R | 24 | GM | AI | | 0-0 | 73-31-11 | D00319D | J01 | | | TB0207Y | A034 | BJ | | 115-199 |
| 3003Y | 24 | GM | NC | | 0-0 | 73-31-11 | D00319D | H01 | | | TB0207Y | A035 | BJ | | 001-099 |
| 3003Y | 24 | GM | AI | | 0-0 | 73-31-11 | D00319D | H01 | | | TB0207Y | A035 | BJ | | 115-199 |
| 3004B | 24 | GM | ND | | 3-5 | 73-31-11 | D41734J | 3 | | | TB0207Y | A036 | BJ | | 001-099 |
| 3004B | 24 | GM | AJ | | 3-4 | 73-31-11 | D41734J | 3 | | | TB0207Y | A036 | BJ | | 115-199 |
| 3004R | 24 | GM | ND | | 0-0 | 73-31-11 | D41734J | 2 | | | TB0207Y | C035 | BJ | | 001-099 |
| 3004R | 24 | GM | AJ | | 0-0 | 73-31-11 | D41734J | 2 | | | TB0207Y | C035 | BJ | | 115-199 |
| 3004Y | 24 | GM | ND | | 0-0 | 73-31-11 | D41734J | 4 | | | TB0207Y | C036 | BJ | | 001-099 |
| 3004Y | 24 | GM | AJ | | 0-0 | 73-31-11 | D41734J | 4 | | | TB0207Y | C036 | BJ | | 115-199 |
| 3005B | 24 | GM | NE | | 3-2 | 73-31-11 | D00319A | J09 | | | TB0207Y | A036 | BJ | | 001-099 |
| 3005B | 24 | GM | AK | | 3-1 | 73-31-11 | D00319A | J09 | | | TB0207Y | A036 | BJ | | 115-199 |
| 3005R | 24 | GM | NE | | 0-0 | 73-31-11 | D00319A | J08 | | | TB0207Y | C035 | BJ | | 001-099 |
| 3005R | 24 | GM | AK | | 0-0 | 73-31-11 | D00319A | J08 | | | TB0207Y | C035 | BJ | | 115-199 |
| 3005Y | 24 | GM | NE | | 0-0 | 73-31-11 | D00319A | J07 | | | TB0207Y | C036 | BJ | | 001-099 |
| 3005Y | 24 | GM | AK | | 0-0 | 73-31-11 | D00319A | J07 | | | TB0207Y | C036 | BJ | | 115-199 |
| 3006B | 24 | GM | NF | | 4-7 | 73-31-11 | D00321A | J09 | | | TB0207Y | A036 | BJ | | 001-099 |
| 3006B | 24 | GM | AL | | 4-6 | 73-31-11 | D00321A | J09 | | | TB0207Y | A036 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 112

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 3006R | 24 | GM | NF | | 0-0 | 73-31-11 | D00321A | J08 | | | TB0207Y | C035 | BJ | | 001-099 |
| 3006R | 24 | GM | AL | | 0-0 | 73-31-11 | D00321A | J08 | | | TB0207Y | C035 | BJ | | 115-199 |
| 3006Y | 24 | GM | NF | | 0-0 | 73-31-11 | D00321A | J07 | | | TB0207Y | C036 | BJ | | 001-099 |
| 3006Y | 24 | GM | AL | | 0-0 | 73-31-11 | D00321A | J07 | | | TB0207Y | C036 | BJ | | 115-199 |
| 3007B | 24 | GM | BI | | 2-6 | 79-31-11 | D41736J | 9 | | | TB0207Z | 77 | BJ | | 115-199 |
| 3007R | 24 | GM | BI | | 0-0 | 79-31-11 | D41736J | 10 | | | TB0207Y | A079 | BJ | | 115-199 |
| 3007Y | 24 | GM | BI | | 0-0 | 79-31-11 | D41736J | 8 | | | GD02211 | DC.. | 2 | | 115-199 |
| 3009B | 24 | GM | BK | | 2-3 | 79-31-11 | D41734J | 9 | | | TB0207Z | 78 | BJ | | 115-199 |
| 3009R | 24 | GM | BK | | 0-0 | 79-31-11 | D41734J | 10 | | | TB0207Y | C079 | BJ | | 115-199 |
| 3009Y | 24 | GM | BK | | 0-0 | 79-31-11 | D41734J | 8 | | | GD02211 | DC.. | 2 | | 115-199 |
| 3011B | 24 | GM | BO | | 4-1 | 79-32-11 | D41736J | 12 | | | TB0207Y | C001 | BJ | | 115-199 |
| 3011R | 24 | GM | BO | | 0-0 | 79-32-11 | D41736J | 11 | | | GD02201 | AC.. | 2 | | 115-199 |
| 3011Y | 24 | GM | BO | | 0-0 | 79-32-11 | D41736J | 13 | | | TB0207Y | A001 | BJ | | 115-199 |
| 3014B | 24 | GM | BR | | 3-10 | 79-32-11 | D41734J | 12 | | | TB0207Y | C002 | BJ | | 115-199 |
| 3014R | 24 | GM | BR | | 0-0 | 79-32-11 | D41734J | 11 | | | GD02201 | AC.. | 2 | | 115-199 |
| 3014Y | 24 | GM | BR | | 0-0 | 79-32-11 | D41734J | 13 | | | TB0207Y | A002 | BJ | | 115-199 |
| 3504B | 24 | G3 | HW | | 3-7 | 23-41-11 | D41660J | 26 | | | D41867J | 6 | | | 115-199 |
| 3504R | 24 | G3 | HW | | 0-0 | 23-41-11 | D41660J | 27 | | | D41867J | 7 | | | 115-199 |
| 3504Y | 24 | G3 | HW | | 0-0 | 23-41-11 | D41660J | 28 | | | D41867J | 8 | | | 115-199 |
| 3504Z | | | HW | | 0-0 | 23-41-11 | D41660J | 22 | | | D41867J | 9 | | | 115-199 |
| 4001B | 24 | GN | QA | | 2-1 | 21-52-31 | D04646B | D05 | | | D42084J | 20 | | | 001-099 |
| 4001B | 24 | GN | IC | | 2-4 | 21-52-31 | D04646B | D05 | | | D42084J | 20 | | | 115-199 |
| 4001G | 24 | GN | QA | | 0-0 | 21-52-31 | D04646B | A05 | | | D42084J | 40 | | | 001-099 |
| 4001G | 24 | GN | IC | | 0-0 | 21-52-31 | D04646B | A05 | | | D42084J | 40 | | | 115-199 |
| 4001R | 24 | GN | QA | | 0-0 | 21-52-31 | D04646B | D06 | | | D42084J | 19 | | | 001-099 |
| 4001R | 24 | GN | IC | | 0-0 | 21-52-31 | D04646B | D06 | | | D42084J | 19 | | | 115-199 |
| 4001Y | 24 | GN | QA | | 0-0 | 21-52-31 | D04646B | A06 | | | D42084J | 21 | | | 001-099 |
| 4001Y | 24 | GN | IC | | 0-0 | 21-52-31 | D04646B | A06 | | | D42084J | 21 | | | 115-199 |
| 4002B | 24 | GN | QB | | 3-8 | 21-52-31 | D04646A | D05 | | | D42086J | 20 | | | 001-099 |
| 4002B | 24 | GN | HZ | | 3-1 | 21-52-31 | D04646A | D05 | | | D42086J | 20 | | | 115-199 |
| 4002G | 24 | GN | QB | | 0-0 | 21-52-31 | D04646A | A05 | | | D42086J | 40 | | | 001-099 |
| 4002G | 24 | GN | HZ | | 0-0 | 21-52-31 | D04646A | A05 | | | D42086J | 40 | | | 115-199 |
| 4002R | 24 | GN | QB | | 0-0 | 21-52-31 | D04646A | D06 | | | D42086J | 19 | | | 001-099 |
| 4002R | 24 | GN | HZ | | 0-0 | 21-52-31 | D04646A | D06 | | | D42086J | 19 | | | 115-199 |
| 4002Y | 24 | GN | QB | | 0-0 | 21-52-31 | D04646A | A06 | | | D42086J | 21 | | | 001-099 |
| 4002Y | 24 | GN | HZ | | 0-0 | 21-52-31 | D04646A | A06 | | | D42086J | 21 | | | 115-199 |
| 4501G | 22 | DU | RA | | 3-3 | 77-21-11 | D41774J | 22 | | | TB0207Y | A070 | BJ | | 001-099 |
| 4501G | 22 | DU | BW | | 3-9 | 77-21-11 | D41774J | 22 | | | TB0207Y | A070 | BJ | | 115-199 |
| 4501W | 22 | DU | RA | | 0-0 | 77-21-11 | D41774J | 19 | | | TB0207Y | A069 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 113

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 4501W | 22 | | DU | BW | 0-0 | 77-21-11 | D41774J | 31 | | | TB0207Y | A069 | BJ | | 115-199 |
| 4501Z | | | | RA | 0-0 | 77-21-11 | D41774J | 23 | | | GD02209 | ST.. | 2 | | 001-099 |
| 4501Z | | | | BW | 0-0 | 77-21-11 | D41774J | 23 | | | GD02209 | ST.. | 2 | | 115-199 |
| 4502G | 22 | | DU | RB | 3-5 | 77-21-11 | D00321E | A15 | | | TB0207Y | A070 | BJ | | 001-099 |
| 4502G | 22 | | DU | BX | 3-5 | 77-21-11 | D00321E | A15 | | | TB0207Y | A070 | BJ | | 115-199 |
| 4502W | 22 | | DU | RB | 0-0 | 77-21-11 | D00321E | B15 | | | TB0207Y | A069 | BJ | | 001-099 |
| 4502W | 22 | | DU | BX | 0-0 | 77-21-11 | D00321E | B15 | | | TB0207Y | A069 | BJ | | 115-199 |
| 4502Z | | | | RB | 0-0 | 77-21-11 | D00321E | DED | | | GD02209 | ST.. | 2 | | 001-099 |
| 4502Z | | | | BX | 0-0 | 77-21-11 | D00321E | DED | | | GD02209 | ST.. | 2 | | 115-199 |
| 4503G | 22 | | DU | RC | 3-10 | 77-21-11 | D42093J | 12 | | | TB0207Y | A070 | BJ | | 001-099 |
| 4503G | 22 | | DU | BY | 4-0 | 77-21-11 | D42093J | 12 | | | TB0207Y | A070 | BJ | | 115-199 |
| 4503W | 22 | | DU | RC | 0-0 | 77-21-11 | D42093J | 11 | | | TB0207Y | A069 | BJ | | 001-099 |
| 4503W | 22 | | DU | BY | 0-0 | 77-21-11 | D42093J | 11 | | | TB0207Y | A069 | BJ | | 115-199 |
| 4503Z | | | | RC | 0-0 | 77-21-11 | D42093J | 10 | | | GD02209 | ST.. | 2 | | 001-099 |
| 4503Z | | | | BY | 0-0 | 77-21-11 | D42093J | 10 | | | GD02209 | ST.. | 2 | | 115-199 |
| 4504G | 22 | | DU | RD | 2-6 | 77-21-11 | D00319E | A15 | | | TB0207Y | A070 | BJ | | 001-099 |
| 4504G | 22 | | DU | BZ | 2-6 | 77-21-11 | D00319E | A15 | | | TB0207Y | A070 | BJ | | 115-199 |
| 4504W | 22 | | DU | RD | 0-0 | 77-21-11 | D00319E | B15 | | | TB0207Y | A069 | BJ | | 001-099 |
| 4504W | 22 | | DU | BZ | 0-0 | 77-21-11 | D00319E | B15 | | | TB0207Y | A069 | BJ | | 115-199 |
| 4504Z | | | | RD | 0-0 | 77-21-11 | D00319E | DED | | | GD02209 | ST.. | 2 | | 001-099 |
| 4504Z | | | | BZ | 0-0 | 77-21-11 | D00319E | DED | | | GD02209 | ST.. | 2 | | 115-199 |
| 4505G | 22 | | DU | RE | 2-5 | 77-21-11 | D00319B | A15 | | | TB0207Y | C069 | BJ | | 001-099 |
| 4505G | 22 | | DU | CA | 2-7 | 77-21-11 | D00319B | A15 | | | TB0207Y | C069 | BJ | | 115-199 |
| 4505W | 22 | | DU | RE | 0-0 | 77-21-11 | D00319B | B15 | | | TB0207Y | C070 | BJ | | 001-099 |
| 4505W | 22 | | DU | CA | 0-0 | 77-21-11 | D00319B | B15 | | | TB0207Y | C070 | BJ | | 115-199 |
| 4505Z | | | | RE | 0-0 | 77-21-11 | D00319B | DED | | | GD02209 | ST.. | 2 | | 001-099 |
| 4505Z | | | | CA | 0-0 | 77-21-11 | D00319B | DED | | | GD02209 | ST.. | 2 | | 115-199 |
| 4506G | 22 | | DU | RF | 2-2 | 77-21-11 | D42073J | 16 | | | TB0207Y | C069 | BJ | | 001-099 |
| 4506G | 22 | | DU | CB | 2-4 | 77-21-11 | D42073J | 16 | | | TB0207Y | C069 | BJ | | 115-199 |
| 4506W | 22 | | DU | RF | 0-0 | 77-21-11 | D42073J | 15 | | | TB0207Y | C070 | BJ | | 001-099 |
| 4506W | 22 | | DU | CB | 0-0 | 77-21-11 | D42073J | 15 | | | TB0207Y | C070 | BJ | | 115-199 |
| 4506Z | | | | RF | 0-0 | 77-21-11 | D42073J | 17 | | | GD02209 | ST.. | 2 | | 001-099 |
| 4506Z | | | | CB | 0-0 | 77-21-11 | D42073J | 17 | | | GD02209 | ST.. | 2 | | 115-199 |
| 4507G | 22 | | DU | RG | 2-2 | 77-21-11 | D41764J | 24 | | | TB0207Y | C069 | BJ | | 001-099 |
| 4507G | 22 | | DU | CC | 3-6 | 77-21-11 | D41764J | 24 | | | TB0207Y | C069 | BJ | | 115-199 |
| 4507W | 22 | | DU | RG | 0-0 | 77-21-11 | D41764J | 23 | | | TB0207Y | C070 | BJ | | 001-099 |
| 4507W | 22 | | DU | CC | 0-0 | 77-21-11 | D41764J | 23 | | | TB0207Y | C070 | BJ | | 115-199 |
| 4507Z | | | | RG | 0-0 | 77-21-11 | D41764J | 22 | | | GD02209 | ST.. | 2 | | 001-099 |
| 4507Z | | | | CC | 0-0 | 77-21-11 | D41764J | 25 | | | GD02209 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 114

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | |
| 4508G | 22 | DU | RH | | 3-6 | 77-21-11 | D00321B | A15 | | | TB0207Y | C069 | BJ | | 001-099 | |
| 4508G | 22 | DU | CD | | 3-6 | 77-21-11 | D00321B | A15 | | | TB0207Y | C069 | BJ | | 115-199 | |
| 4508W | 22 | DU | RH | | 0-0 | 77-21-11 | D00321B | B15 | | | TB0207Y | C070 | BJ | | 001-099 | |
| 4508W | 22 | DU | CD | | 0-0 | 77-21-11 | D00321B | B15 | | | TB0207Y | C070 | BJ | | 115-199 | |
| 4508Z | | | RH | | 0-0 | 77-21-11 | D00321B | DED | | | GD02209 | ST.. | 2 | | 001-099 | |
| 4508Z | | | CD | | 0-0 | 77-21-11 | D00321B | DED | | | GD02209 | ST.. | 2 | | 115-199 | |
| 4521B | 22 | VX | RU | | 2-11 | 77-31-11 | D05602B | B01 | | | D41788J | 27 | | | 001-099 | |
| 4521W | 22 | VX | RU | | 0-0 | 77-31-11 | D05602B | A01 | | | D41788J | 26 | | | 001-099 | |
| 4521Z | | | RU | | 0-0 | 77-31-11 | D05602B | DED | | | D41788J | | | FT | 001-099 | |
| 4522B | 22 | VX | RV | | 2-11 | 77-31-11 | D05602B | B04 | | | D41788J | 29 | | | 001-099 | |
| 4522W | 22 | VX | RV | | 0-0 | 77-31-11 | D05602B | A04 | | | D41788J | 28 | | | 001-099 | |
| 4522Z | | | RV | | 0-0 | 77-31-11 | D05602B | DED | | | D41788J | | | FU | 001-099 | |
| 4523B | 22 | VX | RW | | 2-9 | 77-31-11 | D04240A | B01 | | | D41772J | 27 | | | 001-099 | |
| 4523W | 22 | VX | RW | | 0-0 | 77-31-11 | D04240A | A01 | | | D41772J | 26 | | | 001-099 | |
| 4523Z | | | RW | | 0-0 | 77-31-11 | D04240A | DED | | | D41772J | | | FY | 001-099 | |
| 4524B | 22 | VX | RX | | 2-9 | 77-31-11 | D04240A | B04 | | | D41772J | 29 | | | 001-099 | |
| 4524W | 22 | VX | RX | | 0-0 | 77-31-11 | D04240A | A04 | | | D41772J | 28 | | | 001-099 | |
| 4524Z | | | RX | | 0-0 | 77-31-11 | D04240A | DED | | | D41772J | | | FW | 001-099 | |
| 5001B | 24 | G2 | TA | | 3-0 | 31-31-41 | D00319B | B09 | | | D00791 | 53 | | | 001-099 | |
| 5001B | 24 | G2 | CE | | 3-1 | 31-31-21 | D00319B | B09 | | | D00791 | 53 | | | 115-199 | |
| 5001R | 24 | G2 | TA | | 0-0 | 31-31-41 | D00319B | A09 | | | D00791 | 52 | | | 001-099 | |
| 5001R | 24 | G2 | CE | | 0-0 | 31-31-21 | D00319B | A09 | | | D00791 | 52 | | | 115-199 | |
| 5001Z | | | TA | | 0-0 | 31-31-41 | GD02217 | ST.. | 2 | | D00791 | DED | | | 001-099 | |
| 5001Z | | | CE | | 0-0 | 31-31-21 | GD02217 | ST.. | 2 | | D00791 | DED | | | 115-199 | |
| 5002B | 24 | G2 | TB | | 3-1 | 31-31-41 | D00791 | 108 | | | D00321B | B09 | | | 001-099 | |
| 5002B | 24 | G2 | CF | | 3-1 | 31-31-21 | D00321B | B09 | | | D00791 | 108 | | | 115-199 | |
| 5002R | 24 | G2 | TB | | 0-0 | 31-31-41 | D00791 | 107 | | | D00321B | A09 | | | 001-099 | |
| 5002R | 24 | G2 | CF | | 0-0 | 31-31-21 | D00321B | A09 | | | D00791 | 107 | | | 115-199 | |
| 5002Z | | | TB | | 0-0 | 31-31-41 | D00791 | DED | | | GD02219 | ST.. | 2 | | 001-099 | |
| 5002Z | | | CF | | 0-0 | 31-31-21 | GD02219 | ST.. | 2 | | D00791 | DED | | | 115-199 | |
| 5004B | 24 | G2 | TD | | 3-6 | 22-41-13 | D41317J | 32 | | | TB0207Y | C093 | BJ | | 001-099 | |
| 5004B | 24 | G2 | CH | | 3-7 | 22-41-13 | D41317J | 32 | | | TB0207Y | C093 | BJ | | 115-199 | |
| 5004R | 24 | G2 | TD | | 0-0 | 22-41-13 | D41317J | 31 | | | TB0207Y | A093 | BJ | | 001-099 | |
| 5004R | 24 | G2 | CH | | 0-0 | 22-41-13 | D41317J | 31 | | | TB0207Y | A093 | BJ | | 115-199 | |
| 5004Z | | | TD | | 0-0 | 22-41-13 | D41317J | 33 | | | TB0207Y | | | TM | 001-099 | |
| 5004Z | | | CH | | 0-0 | 22-41-13 | D41317J | 33 | | | GD02213 | ST.. | 2 | | 115-199 | |
| 5005B | 24 | G2 | TE | | 3-2 | 22-41-13 | D00319E | B05 | | | TB0207Y | C093 | BJ | | 001, 003-099 | |
| 5005B | 24 | G2 | TE | | 3-3 | 22-41-13 | D00319E | B05 | | | TB0207Y | C093 | BJ | | 002 | |
| 5005B | 24 | G2 | CI | | 3-2 | 22-41-13 | D00319E | B05 | | | TB0207Y | C093 | BJ | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 115

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1270
Page 116
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5013R | 24 | G2 | TM | | 0-0 | 77-11-11 | D41788J | | 5 | | TB0207Z | 18 | BJ | | 001-099 |
| 5013R | 24 | G2 | CQ | | 0-0 | 77-11-11 | D41788J | | 5 | | TB0207Z | 18 | BJ | | 115-199 |
| 5013Z | | | TM | | 0-0 | 77-11-11 | D41788J | | 6 | | GD02203 | ST.. | 2 | | 001-099 |
| 5013Z | | | CQ | | 0-0 | 77-11-11 | D41788J | | 6 | | GD02203 | ST.. | 2 | | 115-199 |
| 5014B | 24 | G2 | TN | | 4-11 | 77-11-11 | D00321D | | J05 | | TB0207Z | 17 | BJ | | 001-099 |
| 5014B | 24 | G2 | CR | | 4-9 | 77-11-11 | D00321D | | J05 | | TB0207Z | 17 | BJ | | 115-199 |
| 5014R | 24 | G2 | TN | | 0-0 | 77-11-11 | D00321D | | J04 | | TB0207Z | 18 | BJ | | 001-099 |
| 5014R | 24 | G2 | CR | | 0-0 | 77-11-11 | D00321D | | J04 | | TB0207Z | 18 | BJ | | 115-199 |
| 5014Z | | | TN | | 0-0 | 77-11-11 | D00321D | | DED | | GD02203 | ST.. | 2 | | 001-099 |
| 5014Z | | | CR | | 0-0 | 77-11-11 | D00321D | | DED | | GD02203 | ST.. | 2 | | 115-199 |
| 5015B | 24 | G2 | TO | | 3-6 | 77-11-11 | D42023J | | 16 | | TB0207Z | 19 | BJ | | 001-099 |
| 5015B | 24 | G2 | CS | | 3-5 | 77-11-11 | D42023J | | 16 | | TB0207Z | 20 | BJ | | 115-199 |
| 5015R | 24 | G2 | TO | | 0-0 | 77-11-11 | D42023J | | 15 | | TB0207Z | 20 | BJ | | 001-099 |
| 5015R | 24 | G2 | CS | | 0-0 | 77-11-11 | D42023J | | 15 | | TB0207Z | 19 | BJ | | 115-199 |
| 5015Z | | | TO | | 0-0 | 77-11-11 | D42023J | | 17 | | GD02203 | ST.. | 2 | | 001-099 |
| 5015Z | | | CS | | 0-0 | 77-11-11 | D42023J | | 17 | | GD02203 | ST.. | 2 | | 115-199 |
| 5016B | 24 | G2 | TP | | 5-0 | 77-11-11 | D00321A | | J03 | | TB0207Z | 19 | BJ | | 001-099 |
| 5016B | 24 | G2 | CT | | 4-10 | 77-11-11 | D00321A | | J03 | | TB0207Z | 20 | BJ | | 115-199 |
| 5016R | 24 | G2 | TP | | 0-0 | 77-11-11 | D00321A | | J04 | | TB0207Z | 20 | BJ | | 001-099 |
| 5016R | 24 | G2 | CT | | 0-0 | 77-11-11 | D00321A | | J04 | | TB0207Z | 19 | BJ | | 115-199 |
| 5016Z | | | TP | | 0-0 | 77-11-11 | D00321A | | DED | | GD02203 | ST.. | 2 | | 001-099 |
| 5016Z | | | CT | | 0-0 | 77-11-11 | D00321A | | DED | | GD02203 | ST.. | 2 | | 115-199 |
| 5017B | 24 | G2 | CU | | 3-3 | 31-31-22 | D41317J | | 35 | | TB0207Z | 20 | BJ | | 115-199 |
| 5017R | 24 | G2 | CU | | 0-0 | 31-31-22 | D41317J | | 36 | | TB0207Z | 19 | BJ | | 115-199 |
| 5017Z | | | CU | | 0-0 | 31-31-22 | D41317J | | 37 | | GD02203 | ST.. | 2 | | 115-199 |
| 5018B | 24 | G2 | TR | | 3-7 | 77-11-11 | D00319A | | J03 | | TB0207Z | 19 | BJ | | 001-099 |
| 5018B | 24 | G2 | CV | | 3-6 | 77-11-11 | D00319A | | J03 | | TB0207Z | 20 | BJ | | 115-199 |
| 5018R | 24 | G2 | TR | | 0-0 | 77-11-11 | D00319A | | J04 | | TB0207Z | 20 | BJ | | 001-099 |
| 5018R | 24 | G2 | CV | | 0-0 | 77-11-11 | D00319A | | J04 | | TB0207Z | 19 | BJ | | 115-199 |
| 5018Z | | | TR | | 0-0 | 77-11-11 | D00319A | | DED | | GD02203 | ST.. | 2 | | 001-099 |
| 5018Z | | | CV | | 0-0 | 77-11-11 | D00319A | | DED | | GD02203 | ST.. | 2 | | 115-199 |
| 5019B | 24 | G2 | TS | | 2-9 | 77-11-11 | D41772J | | 4 | | TB0207Z | 19 | BJ | | 001-099 |
| 5019B | 24 | G2 | CW | | 2-7 | 77-11-11 | D41772J | | 4 | | TB0207Z | 20 | BJ | | 115-199 |
| 5019R | 24 | G2 | TS | | 0-0 | 77-11-11 | D41772J | | 5 | | TB0207Z | 20 | BJ | | 001-099 |
| 5019R | 24 | G2 | CW | | 0-0 | 77-11-11 | D41772J | | 5 | | TB0207Z | 19 | BJ | | 115-199 |
| 5019Z | | | TS | | 0-0 | 77-11-11 | D41772J | | 6 | | GD02203 | ST.. | 2 | | 001-099 |
| 5019Z | | | CW | | 0-0 | 77-11-11 | D41772J | | 6 | | GD02203 | ST.. | 2 | | 115-199 |
| 5028B | 24 | G2 | UB | | 2-4 | 28-41-11 | D41628J | | 50 | | TB0207Y | A072 | BJ | | 001-099 |
| 5028B | 24 | G2 | SE | | 2-7 | 28-41-11 | D41628J | | 50 | | TB0207Y | A072 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 117

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5028R | 24 | G2 | UB | | 0-0 | 28-41-11 | D41628J | 51 | | | TB0207Y | A071 | BJ | | 001-099 |
| 5028R | 24 | G2 | SE | | 0-0 | 28-41-11 | D41628J | 51 | | | TB0207Y | A071 | BJ | | 115-199 |
| 5028Z | | | UB | | 0-0 | 28-41-11 | D41628J | 52 | | | TB0207Y | | | UA | 001-099 |
| 5028Z | | | SE | | 0-0 | 28-41-11 | D41628J | 52 | | | TB0207Y | | | UA | 115-199 |
| 5029B | 24 | G2 | UC | | 4-1 | 28-41-11 | D41867J | 47 | | | TB0207Y | A072 | BJ | | 001, 003-099 |
| 5029B | 24 | G2 | UC | | 4-2 | 28-41-11 | D41867J | 47 | | | TB0207Y | A072 | BJ | | 002 |
| 5029B | 24 | G2 | SF | | 4-4 | 28-41-11 | D41867J | 47 | | | TB0207Y | A072 | BJ | | 115-199 |
| 5029R | 24 | G2 | UC | | 0-0 | 28-41-11 | D41867J | 48 | | | TB0207Y | A071 | BJ | | 001-099 |
| 5029R | 24 | G2 | SF | | 0-0 | 28-41-11 | D41867J | 48 | | | TB0207Y | A071 | BJ | | 115-199 |
| 5029Z | | | UC | | 0-0 | 28-41-11 | D41867J | 49 | | | TB0207Y | | | UA | 001-099 |
| 5029Z | | | SF | | 0-0 | 28-41-11 | D41867J | 49 | | | TB0207Y | | | UA | 115-199 |
| 5031B | 24 | G2 | UE | | 4-8 | 31-41-19 | D41065J | 11 | | | D00321E | F08 | | | 001-099 |
| 5031B | 24 | G2 | DQ | | 4-6 | 31-41-19 | D00321E | F08 | | | D41065J | 11 | | | 115-199 |
| 5031R | 24 | G2 | UE | | 0-0 | 31-41-19 | D41065J | 10 | | | D00321E | F07 | | | 001-099 |
| 5031R | 24 | G2 | DQ | | 0-0 | 31-41-19 | D00321E | F07 | | | D41065J | 10 | | | 115-199 |
| 5031Z | | | UE | | 0-0 | 31-41-19 | D41065J | | | DQ | D00321E | DED | | | 001-099 |
| 5031Z | | | DQ | | 0-0 | 31-41-19 | D00321E | DED | | | D41065J | | | DQ | 115-199 |
| 5032B | 24 | G2 | UF | | 3-3 | 31-41-19 | D41065J | 9 | | | D00319E | F08 | | | 001-099 |
| 5032B | 24 | G2 | DR | | 3-2 | 31-41-19 | D00319E | F08 | | | D41065J | 9 | | | 115-199 |
| 5032R | 24 | G2 | UF | | 0-0 | 31-41-19 | D41065J | 8 | | | D00319E | F07 | | | 001-099 |
| 5032R | 24 | G2 | DR | | 0-0 | 31-41-19 | D00319E | F07 | | | D41065J | 8 | | | 115-199 |
| 5032Z | | | UF | | 0-0 | 31-41-19 | D00319E | DED | | | D41065J | | | DR | 001-099 |
| 5032Z | | | DR | | 0-0 | 31-41-19 | D00319E | DED | | | D41065J | | | DR | 115-199 |
| 5033B | 24 | G2 | UG | | 2-9 | 31-41-12 | D00319E | F04 | | | D41317J | 2 | | | 001-099 |
| 5033B | 24 | G2 | DS | | 2-10 | 31-41-12 | D00319E | F04 | | | D41317J | 2 | | | 115-199 |
| 5033R | 24 | G2 | UG | | 0-0 | 31-41-12 | D00319E | F03 | | | D41317J | 1 | | | 001-099 |
| 5033R | 24 | G2 | DS | | 0-0 | 31-41-12 | D00319E | F03 | | | D41317J | 1 | | | 115-199 |
| 5033Z | | | UG | | 0-0 | 31-41-12 | D00319E | DED | | | D41317J | | | DS | 001-099 |
| 5033Z | | | DS | | 0-0 | 31-41-12 | D00319E | DED | | | D41317J | | | DS | 115-199 |
| 5034B | 24 | G2 | UH | | 2-9 | 31-41-12 | D00319E | B11 | | | D41317J | 5 | | | 001-099 |
| 5034B | 24 | G2 | DT | | 2-10 | 31-41-12 | D00319E | B11 | | | D41317J | 5 | | | 115-199 |
| 5034R | 24 | G2 | UH | | 0-0 | 31-41-12 | D00319E | B10 | | | D41317J | 4 | | | 001-099 |
| 5034R | 24 | G2 | DT | | 0-0 | 31-41-12 | D00319E | B10 | | | D41317J | 4 | | | 115-199 |
| 5034Z | | | UH | | 0-0 | 31-41-12 | D00319E | DED | | | D41317J | | | DT | 001-099 |
| 5034Z | | | DT | | 0-0 | 31-41-12 | D00319E | DED | | | D41317J | | | DT | 115-199 |
| 5035B | 24 | G2 | UI | | 5-0 | 31-41-22 | D00321E | F04 | | | D41369J | 5 | | | 001-099 |
| 5035B | 24 | G2 | EK | | 5-2 | 31-41-22 | D00321E | F04 | | | D41369J | 5 | | | 115-199 |
| 5035R | 24 | G2 | UI | | 0-0 | 31-41-22 | D00321E | F03 | | | D41369J | 4 | | | 001-099 |
| 5035R | 24 | G2 | EK | | 0-0 | 31-41-22 | D00321E | F03 | | | D41369J | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 118

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|-------------------------------------|---------------|---------------------------|------------------------------|
| Wire No. | GA CO TY | Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice |
| W1275 | 286N1275 | E4-2 SHELF -(N2) (continued) | | | |
| 5041R | 24 | G2 | EZ | 0-0 31-41-12 D00319E F05 | TB0207Y C071 BJ 115-199 |
| 5041Z | | | UO | 0-0 31-41-12 D00319E DED | GD02210 ST.. 2 001-099 |
| 5041Z | | | EZ | 0-0 31-41-12 D00319E DED | GD02211 ST.. 2 115-199 |
| 5042B | 24 | G2 | UP | 2-11 28-41-11 D00321E F02 | TB0207Y A072 BJ 001, 003-099 |
| 5042B | 24 | G2 | UP | 3-0 28-41-11 D00321E F02 | TB0207Y A072 BJ 002 |
| 5042B | 24 | G2 | FR | 3-1 28-41-11 D00321E F02 | TB0207Y A072 BJ 115-199 |
| 5042R | 24 | G2 | UP | 0-0 28-41-11 D00321E F01 | TB0207Y A071 BJ 001-099 |
| 5042R | 24 | G2 | FR | 0-0 28-41-11 D00321E F01 | TB0207Y A071 BJ 115-199 |
| 5042Z | | | UP | 0-0 28-41-11 D00321E DED | TB0207Y UA 001-099 |
| 5042Z | | | FR | 0-0 28-41-11 D00321E DED | TB0207Y UA 115-199 |
| 5043B | 24 | G2 | UQ | 2-9 28-41-11 D00319E F02 | TB0207Y A072 BJ 001, 003-099 |
| 5043B | 24 | G2 | UQ | 2-10 28-41-11 D00319E F02 | TB0207Y A072 BJ 002 |
| 5043B | 24 | G2 | FS | 2-11 28-41-11 D00319E F02 | TB0207Y A072 BJ 115-199 |
| 5043R | 24 | G2 | UQ | 0-0 28-41-11 D00319E F01 | TB0207Y A071 BJ 001-099 |
| 5043R | 24 | G2 | FS | 0-0 28-41-11 D00319E F01 | TB0207Y A071 BJ 115-199 |
| 5043Z | | | UQ | 0-0 28-41-11 D00319E DED | TB0207Y UA 001-099 |
| 5043Z | | | FS | 0-0 28-41-11 D00319E DED | TB0207Y UA 115-199 |
| 5045B | 24 | G2 | US | 4-4 77-31-11 D00321E B03 | TB0207Y A026 BJ 001-099 |
| 5045B | 24 | G2 | FX | 4-4 77-31-11 D00321E B03 | TB0207Y A026 BJ 115-199 |
| 5045R | 24 | G2 | US | 0-0 77-31-11 D00321E B02 | TB0207Y A025 BJ 001-099 |
| 5045R | 24 | G2 | FX | 0-0 77-31-11 D00321E B02 | TB0207Y A025 BJ 115-199 |
| 5045Z | | | US | 0-0 77-31-11 D00321E DED | TB0207Y TI 001-099 |
| 5045Z | | | FX | 0-0 77-31-11 D00321E DED | GD02204 ST.. 2 115-199 |
| 5046B | 24 | G2 | UT | 2-5 77-31-11 D04240A D06 | TB0207Y A026 BJ 001, 003-099 |
| 5046B | 24 | G2 | UT | 2-6 77-31-11 D04240A D06 | TB0207Y A026 BJ 002 |
| 5046B | 24 | G2 | HR | 2-6 77-31-11 D04240A D06 | TB0207Y A026 BJ 115-199 |
| 5046R | 24 | G2 | UT | 0-0 77-31-11 D04240A C06 | TB0207Y A025 BJ 001-099 |
| 5046R | 24 | G2 | HR | 0-0 77-31-11 D04240A C06 | TB0207Y A025 BJ 115-199 |
| 5046Z | | | UT | 0-0 77-31-11 D04240A DED | TB0207Y TI 001-099 |
| 5046Z | | | HR | 0-0 77-31-11 D04240A DED | GD02204 ST.. 2 115-199 |
| 5047B | 24 | G2 | UU | 2-11 77-31-11 D00319E B03 | TB0207Y A026 BJ 001, 003-099 |
| 5047B | 24 | G2 | UU | 3-0 77-31-11 D00319E B03 | TB0207Y A026 BJ 002 |
| 5047B | 24 | G2 | FZ | 3-0 77-31-11 D00319E B03 | TB0207Y A026 BJ 115-199 |
| 5047R | 24 | G2 | UU | 0-0 77-31-11 D00319E B02 | TB0207Y A025 BJ 001-099 |
| 5047R | 24 | G2 | FZ | 0-0 77-31-11 D00319E B02 | TB0207Y A025 BJ 115-199 |
| 5047Z | | | UU | 0-0 77-31-11 D00319E DED | TB0207Y TI 001-099 |
| 5047Z | | | FZ | 0-0 77-31-11 D00319E DED | GD02204 ST.. 2 115-199 |
| 5049B | 24 | G2 | UW | 2-10 34-61-14 D00319B C11 | D41317J 11 001-099 |
| 5049B | 24 | G2 | HS | 2-10 34-61-14 D00319B C11 | D41317J 11 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 120

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5049R | 24 | G2 | UW | | 0-0 | 34-61-14 | D00319B | C10 | | | D41317J | 10 | | | 001-099 |
| 5049R | 24 | G2 | HS | | 0-0 | 34-61-14 | D00319B | C10 | | | D41317J | 10 | | | 115-199 |
| 5049Z | | | UW | | 0-0 | 34-61-14 | D00319B | DED | | | D41317J | | | HS | 001-099 |
| 5049Z | | | HS | | 0-0 | 34-61-14 | D00319B | DED | | | D41317J | | | HS | 115-199 |
| 5050B | 24 | G2 | UX | | 5-1 | 34-61-24 | D41369J | 8 | | | D00321B | C11 | | | 001-099 |
| 5050B | 24 | G2 | JA | | 5-3 | 34-61-24 | D00321B | C11 | | | D41369J | 8 | | | 115-199 |
| 5050R | 24 | G2 | UX | | 0-0 | 34-61-24 | D41369J | 7 | | | D00321B | C10 | | | 001-099 |
| 5050R | 24 | G2 | JA | | 0-0 | 34-61-24 | D00321B | C10 | | | D41369J | 7 | | | 115-199 |
| 5050Z | | | UX | | 0-0 | 34-61-24 | D00321B | DED | | | D41369J | | | JA | 001-099 |
| 5050Z | | | JA | | 0-0 | 34-61-24 | D00321B | DED | | | D41369J | | | JA | 115-199 |
| 5051B | 24 | G2 | UY | | 5-0 | 34-61-25 | D41369J | 15 | | | D00321E | B09 | | | 001-099 |
| 5051B | 24 | G2 | JB | | 5-2 | 34-61-25 | D00321E | B09 | | | TB0207Y | C045 | BJ | | 115-199 |
| 5051R | 24 | G2 | UY | | 0-0 | 34-61-25 | D41369J | 14 | | | D00321E | B08 | | | 001-099 |
| 5051R | 24 | G2 | JB | | 0-0 | 34-61-25 | D00321E | B08 | | | TB0207Y | C046 | BJ | | 115-199 |
| 5051Z | | | UY | | 0-0 | 34-61-25 | D00321E | DED | | | D41369J | | | JB | 001-099 |
| 5051Z | | | JB | | 0-0 | 34-61-25 | GD02214 | ST.. | 2 | | GD02204 | ST.. | 2 | | 115-199 |
| 5053B | 24 | G2 | VA | | 2-9 | 31-31-41 | D41451J | 7 | | | D00791 | 55 | | | 001-099 |
| 5053B | 24 | G2 | MA | | 2-9 | 31-31-21 | D41451J | 7 | | | D00791 | 55 | | | 115-199 |
| 5053R | 24 | G2 | VA | | 0-0 | 31-31-41 | D41451J | 8 | | | D00791 | 54 | | | 001-099 |
| 5053R | 24 | G2 | MA | | 0-0 | 31-31-21 | D41451J | 8 | | | D00791 | 54 | | | 115-199 |
| 5053Z | | | VA | | 0-0 | 31-31-41 | D41451J | | | CA | D00791 | DED | | | 001-099 |
| 5053Z | | | MA | | 0-0 | 31-31-21 | D41451J | | | CA | D00791 | DED | | | 115-199 |
| 5059B | 24 | G2 | VF | | 2-3 | 31-41-13 | D00319B | C13 | | | TB0207Z | 54 | % | | 001, 003-099 |
| 5059B | 24 | G2 | VF | | 2-4 | 31-41-13 | D00319B | C13 | | | TB0207Z | 54 | % | | 002 |
| 5059B | 24 | G2 | GB | | 3-0 | 31-41-13 | D00319B | C13 | | | TB0207Z | CAP | Y | | 115-199 |
| 5059R | 24 | G2 | VF | | 0-0 | 31-41-13 | D00319B | C12 | | | TB0207Z | 53 | % | | 001-099 |
| 5059R | 24 | G2 | GB | | 0-0 | 31-41-13 | D00319B | C12 | | | TB0207Z | CAP | Y | | 115-199 |
| 5059Z | | | VF | | 0-0 | 31-41-13 | D00319B | DED | | | GD02208 | ST.. | # | | 001-099 |
| 5059Z | | | GB | | 0-0 | 31-41-13 | D00319B | DED | | | GD02208 | ST.. | # | | 115-199 |
| 5064B | 24 | G2 | VK | | 3-0 | 31-41-23 | D00321B | C13 | | | TB0207Y | A082 | % | | 001, 003-099 |
| 5064B | 24 | G2 | VK | | 3-1 | 31-41-23 | D00321B | C13 | | | TB0207Y | A082 | % | | 002 |
| 5064B | 24 | G2 | GG | | 4-0 | 31-41-23 | D00321B | C13 | | | TB0207Z | CAP | Y | | 115-199 |
| 5064R | 24 | G2 | VK | | 0-0 | 31-41-23 | D00321B | C12 | | | TB0207Y | A081 | % | | 001-099 |
| 5064R | 24 | G2 | GG | | 0-0 | 31-41-23 | D00321B | C12 | | | TB0207Z | CAP | Y | | 115-199 |
| 5064Z | | | VK | | 0-0 | 31-41-23 | D00321B | DED | | | GD02211 | ST.. | 2 | | 001-099 |
| 5064Z | | | GG | | 0-0 | 31-41-23 | D00321B | DED | | | GD02211 | ST.. | 2 | | 115-199 |
| 5065B | 24 | G2 | VL | | 2-4 | 34-25-11 | D00319E | F12 | | | TB0207Z | 54 | BJ | | 001, 003-099 |
| 5065B | 24 | G2 | VL | | 2-4 | 34-25-13 | D00319E | F12 | | | TB0207Y | C052 | BJ | | 002 |
| 5065B | 24 | G2 | NC | | 2-7 | 34-25-11 | D00319E | F12 | | | D41879J | 8 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 121

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|--------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5065R | 24 | G2 | VL | | 0-0 | 34-25-11 | D00319E | F11 | | | TB0207Z | 53 | BJ | | 001, 003-099 |
| 5065R | 24 | G2 | VL | | 0-0 | 34-25-13 | D00319E | F11 | | | TB0207Y | C053 | BJ | | 002 |
| 5065R | 24 | G2 | NC | | 0-0 | 34-25-11 | D00319E | F11 | | | D41879J | 7 | | | 115-199 |
| 5065Z | | | VL | | 0-0 | 34-25-11 | D00319E | DED | | | GD02208 | ST.. | 2 | | 001, 003-099 |
| 5065Z | | | VL | | 0-0 | 34-25-13 | D00319E | DED | | | GD02208 | ST.. | 2 | | 002 |
| 5065Z | | | NC | | 0-0 | 34-25-11 | D00319E | DED | | | D41879J | | | JC | 115-199 |
| 5066B | 24 | G2 | VM | | 3-5 | 34-25-11 | D00321E | F12 | | | TB0207Z | 54 | BJ | | 001, 003-099 |
| 5066B | 24 | G2 | VM | | 3-6 | 34-25-13 | D00321E | F12 | | | TB0207Y | C052 | BJ | | 002 |
| 5066B | 24 | G2 | ND | | 5-2 | 34-25-11 | D00321E | F12 | | | D41867J | 14 | | | 115-199 |
| 5066R | 24 | G2 | VM | | 0-0 | 34-25-11 | D00321E | F11 | | | TB0207Z | 53 | BJ | | 001, 003-099 |
| 5066R | 24 | G2 | VM | | 0-0 | 34-25-13 | D00321E | F11 | | | TB0207Y | C053 | BJ | | 002 |
| 5066R | 24 | G2 | ND | | 0-0 | 34-25-11 | D00321E | F11 | | | D41867J | 13 | | | 115-199 |
| 5066Z | | | VM | | 0-0 | 34-25-11 | D00321E | DED | | | GD02207 | ST.. | 2 | | 001, 003-099 |
| 5066Z | | | VM | | 0-0 | 34-25-13 | D00321E | DED | | | GD02207 | ST.. | 2 | | 002 |
| 5066Z | | | ND | | 0-0 | 34-25-11 | D00321E | DED | | | D41867J | | | JD | 115-199 |
| 5067B | 24 | G2 | VN | | 2-7 | 77-11-11 | D00321D | J07 | | | TB0207Z | 118 | BJ | | 001, 003-099 |
| 5067B | 24 | G2 | VN | | 2-8 | 77-11-11 | D00321D | J07 | | | TB0207Z | 118 | BJ | | 002 |
| 5067B | 24 | G2 | KD | | 2-7 | 77-11-11 | D00321D | J07 | | | TB0207Z | 118 | BJ | | 115-199 |
| 5067R | 24 | G2 | VN | | 0-0 | 77-11-11 | D00321D | J06 | | | TB0207Z | 117 | BJ | | 001-099 |
| 5067R | 24 | G2 | KD | | 0-0 | 77-11-11 | D00321D | J06 | | | TB0207Z | 117 | BJ | | 115-199 |
| 5067Z | | | VN | | 0-0 | 77-11-11 | D00321D | DED | | | GD02215 | ST.. | 2 | | 001-099 |
| 5067Z | | | KD | | 0-0 | 77-11-11 | D00321D | DED | | | GD02215 | ST.. | 2 | | 115-199 |
| 5068B | 24 | G2 | VO | | 3-2 | 77-11-11 | D00321A | J02 | | | TB0207Y | C086 | BJ | | 001-099 |
| 5068B | 24 | G2 | KE | | 3-4 | 77-11-11 | D00321A | J02 | | | TB0207Y | C086 | BJ | | 115-199 |
| 5068R | 24 | G2 | VO | | 0-0 | 77-11-11 | D00321A | J01 | | | TB0207Y | A086 | BJ | | 001-099 |
| 5068R | 24 | G2 | KE | | 0-0 | 77-11-11 | D00321A | J01 | | | TB0207Y | A086 | BJ | | 115-199 |
| 5068Z | | | VO | | 0-0 | 77-11-11 | D00321A | DED | | | GD02211 | ST.. | 2 | | 001-099 |
| 5068Z | | | KE | | 0-0 | 77-11-11 | D00321A | DED | | | GD02213 | ST.. | 2 | | 115-199 |
| 5069B | 24 | G2 | VP | | 3-9 | 77-11-11 | D00319D | J07 | | | TB0207Z | 118 | BJ | | 001, 003-099 |
| 5069B | 24 | G2 | VP | | 3-10 | 77-11-11 | D00319D | J07 | | | TB0207Z | 118 | BJ | | 002 |
| 5069B | 24 | G2 | KF | | 3-8 | 77-11-11 | D00319D | J07 | | | TB0207Z | 118 | BJ | | 115-199 |
| 5069R | 24 | G2 | VP | | 0-0 | 77-11-11 | D00319D | J06 | | | TB0207Z | 117 | BJ | | 001-099 |
| 5069R | 24 | G2 | KF | | 0-0 | 77-11-11 | D00319D | J06 | | | TB0207Z | 117 | BJ | | 115-199 |
| 5069Z | | | VP | | 0-0 | 77-11-11 | D00319D | DED | | | GD02215 | ST.. | 2 | | 001-099 |
| 5069Z | | | KF | | 0-0 | 77-11-11 | D00319D | DED | | | GD02215 | ST.. | 2 | | 115-199 |
| 5070B | 24 | G2 | VQ | | 2-10 | 77-11-11 | D00319A | J02 | | | TB0207Y | C086 | BJ | | 001-099 |
| 5070B | 24 | G2 | KG | | 3-0 | 77-11-11 | D00319A | J02 | | | TB0207Y | C086 | BJ | | 115-199 |
| 5070R | 24 | G2 | VQ | | 0-0 | 77-11-11 | D00319A | J01 | | | TB0207Y | A086 | BJ | | 001-099 |
| 5070R | 24 | G2 | KG | | 0-0 | 77-11-11 | D00319A | J01 | | | TB0207Y | A086 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 122

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1270
Page 123
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|--|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | |
| 5080B | 24 | G2 | WB | | 3-4 | 77-31-11 | D00321E | F10 | | | TB0207Y | A068 | BJ | | 001, 003-099 | |
| 5080B | 24 | G2 | WB | | 3-5 | 77-31-11 | D00321E | F10 | | | TB0207Y | A068 | BJ | | 002 | |
| 5080B | 24 | G2 | RE | | 3-5 | 77-31-11 | D00321E | F10 | | | TB0207Y | A068 | BJ | | 115-199 | |
| 5080R | 24 | G2 | WB | | 0-0 | 77-31-11 | D00321E | F09 | | | TB0207Y | C068 | BJ | | 001-099 | |
| 5080R | 24 | G2 | RE | | 0-0 | 77-31-11 | D00321E | F09 | | | TB0207Y | C068 | BJ | | 115-199 | |
| 5080Z | | | WB | | 0-0 | 77-31-11 | D00321E | DED | | | TB0207Y | | | TD | 001-099 | |
| 5080Z | | | RE | | 0-0 | 77-31-11 | D00321E | DED | | | GD02211 | ST.. | 2 | | 115-199 | |
| 5081B | 24 | G2 | WC | | 2-5 | 77-31-11 | D00319E | F10 | | | TB0207Y | A068 | BJ | | 001, 003-099 | |
| 5081B | 24 | G2 | WC | | 2-6 | 77-31-11 | D00319E | F10 | | | TB0207Y | A068 | BJ | | 002 | |
| 5081B | 24 | G2 | RF | | 2-6 | 77-31-11 | D00319E | F10 | | | TB0207Y | A068 | BJ | | 115-199 | |
| 5081R | 24 | G2 | WC | | 0-0 | 77-31-11 | D00319E | F09 | | | TB0207Y | C068 | BJ | | 001-099 | |
| 5081R | 24 | G2 | RF | | 0-0 | 77-31-11 | D00319E | F09 | | | TB0207Y | C068 | BJ | | 115-199 | |
| 5081Z | | | WC | | 0-0 | 77-31-11 | D00319E | DED | | | TB0207Y | | | TD | 001-099 | |
| 5081Z | | | RF | | 0-0 | 77-31-11 | D00319E | DED | | | GD02211 | ST.. | 2 | | 115-199 | |
| 5082B | 24 | G2 | WD | | 3-8 | 77-31-11 | D05602A | D06 | | | TB0207Y | A068 | BJ | | 001, 003-099 | |
| 5082B | 24 | G2 | WD | | 3-9 | 77-31-11 | D05602A | D06 | | | TB0207Y | A068 | BJ | | 002 | |
| 5082B | 24 | G2 | RG | | 3-10 | 77-31-11 | D05602A | D06 | | | TB0207Y | A068 | BJ | | 115-199 | |
| 5082R | 24 | G2 | WD | | 0-0 | 77-31-11 | D05602A | C06 | | | TB0207Y | C068 | BJ | | 001-099 | |
| 5082R | 24 | G2 | RG | | 0-0 | 77-31-11 | D05602A | C06 | | | TB0207Y | C068 | BJ | | 115-199 | |
| 5082Z | | | WD | | 0-0 | 77-31-11 | D05602A | DED | | | TB0207Y | | | TD | 001-099 | |
| 5082Z | | | RG | | 0-0 | 77-31-11 | D05602A | DED | | | GD02211 | ST.. | 2 | | 115-199 | |
| 5103B | 24 | G2 | WE | | 2-5 | 34-25-11 | D41879J | 8 | | | TB0207Z | 54 | BJ | | 001, 003-099 | |
| 5103R | 24 | G2 | WE | | 0-0 | 34-25-11 | D41879J | 7 | | | TB0207Z | 53 | BJ | | 001, 003-099 | |
| 5103Z | | | WE | | 0-0 | 34-25-11 | D41879J | 6 | | | GD02207 | ST.. | 2 | | 001, 003-099 | |
| 5111B | 22 | GU | CZ | | 3-0 | 34-25-13 | D42185J | 12 | | | TB0207Y | C052 | BJ | | 002 | |
| 5111R | 22 | GU | CZ | | 0-0 | 34-25-13 | D42185J | 11 | | | TB0207Y | C053 | BJ | | 002 | |
| 5111Z | | | CZ | | 0-0 | 34-25-13 | D42185J | 13 | | | GD02207 | ST.. | 2 | | 002 | |
| 5131B | 24 | G2 | CM | | 6-0 | 34-61-15 | TB0207Y | C052 | BJ | | D00321F | H03 | | | 115-199 | |
| 5131R | 24 | G2 | CM | | 0-0 | 34-61-15 | TB0207Y | C051 | BJ | | D00321F | H02 | | | 115-199 | |
| 5131Z | | | CM | | 0-0 | 34-61-15 | GD02207 | ST.. | 2 | | GD02213 | ST.. | 2 | | 115-199 | |
| 5133B | 24 | G2 | CG | | 5-0 | 34-61-15 | D41317J | 20 | | | TB0207Y | C052 | BJ | | 115-199 | |
| 5133R | 24 | G2 | CG | | 0-0 | 34-61-15 | D41317J | 19 | | | TB0207Y | C051 | BJ | | 115-199 | |
| 5133Z | | | CG | | 0-0 | 34-61-15 | D41317J | | | EV | GD02207 | ST.. | 2 | | 115-199 | |
| 5134B | 24 | G2 | BT | | 5-0 | 34-61-25 | TB0207Y | C045 | BJ | | D00319F | H03 | | | 115-199 | |
| 5134R | 24 | G2 | BT | | 0-0 | 34-61-25 | TB0207Y | C046 | BJ | | D00319F | H02 | | | 115-199 | |
| 5134Z | | | BT | | 0-0 | 34-61-25 | GD02204 | ST.. | 2 | | GD02208 | ST.. | 2 | | 115-199 | |
| 5135B | 24 | G2 | BS | | 6-0 | 34-61-25 | TB0207Y | C045 | BJ | | D41369J | 15 | | | 115-199 | |
| 5135R | 24 | G2 | BS | | 0-0 | 34-61-25 | TB0207Y | C046 | BJ | | D41369J | 14 | | | 115-199 | |
| 5135Z | | | BS | | 0-0 | 34-61-25 | GD02204 | ST.. | 2 | | D41369J | | | JB | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 124

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5504 | 24 | | GK | | 2-4 | 27-38-11 | D00319E | | H06 | | TB0207Y | C059 | BJ | | 001-099 |
| 5504 | 24 | | GK | | 2-5 | 27-38-11 | D00319E | | H06 | | TB0207Y | C059 | BJ | | 115-199 |
| 5505 | 24 | | GK | | 3-6 | 27-38-11 | D00321E | | H06 | | TB0207Y | C059 | BJ | | 001-099 |
| 5505 | 24 | | GK | | 3-7 | 27-38-11 | D00321E | | H06 | | TB0207Y | C059 | BJ | | 115-199 |
| 5507 | 24 | | GK | | 3-9 | 27-51-31 | D00321E | | D09 | | D41698J | 30 | | *M | 001-099 |
| 5507 | 24 | | GK | | 3-8 | 27-51-31 | D00321E | | D09 | | D41698J | 38 | | *M | 115-199 |
| 5508 | 24 | | GK | | 2-10 | 27-51-31 | D00319E | | D09 | | D41698J | 30 | | *M | 001-099 |
| 5508 | 24 | | GK | | 2-9 | 27-51-31 | D00319E | | D09 | | D41698J | 38 | | *M | 115-199 |
| 5509 | 22 | | GA | | 3-6 | 27-23-11 | D40584J | | 13 | | TB0207Y | A060 | BJ | | 001-099 |
| 5509 | 22 | | GA | | 3-8 | 27-23-11 | D40584J | | 13 | | TB0207Y | A060 | BJ | | 115-199 |
| 5510 | 24 | | GK | | 3-7 | 27-23-11 | D00321B | | J12 | | TB0207Y | A060 | BJ | | 001-099 |
| 5510 | 24 | | GK | | 3-8 | 27-23-11 | D00321B | | J12 | | TB0207Y | A060 | BJ | | 115-199 |
| 5511 | 24 | | GK | | 2-4 | 27-23-11 | D00319B | | J12 | | TB0207Y | A060 | BJ | | 001-099 |
| 5511 | 24 | | GK | | 2-6 | 27-23-11 | D00319B | | J12 | | TB0207Y | A060 | BJ | | 115-199 |
| 5513 | 24 | | GK | | 3-3 | 27-23-11 | D00321F | | J08 | | D41628J | 12 | | *J | 001-099 |
| 5513 | 24 | | GK | | 3-4 | 27-23-11 | D00321F | | J08 | | D41628J | 37 | | *J | 115-199 |
| 5514 | 24 | | GK | | 2-4 | 27-23-11 | D00319F | | J08 | | D41628J | 12 | | *J | 001-099 |
| 5514 | 24 | | GK | | 2-5 | 27-23-11 | D00319F | | J08 | | D41628J | 37 | | *J | 115-199 |
| 5516 | 24 | | GK | | 3-5 | 27-23-11 | D00321D | | H05 | | D41720J | 4 | | *N | ALL |
| 5517 | 24 | | GK | | 3-1 | 27-23-11 | D00319D | | H05 | | D41720J | 4 | | *N | ALL |
| 5526 | 24 | | GK | | 3-8 | 34-61-25 | D00319B | | K01 | | D41369J | 17 | | *G | 001-099 |
| 5526 | 24 | | GK | | 3-10 | 34-61-25 | D00319B | | K01 | | D41369J | 17 | | *G | 115-199 |
| 5527 | 24 | | GK | | 5-1 | 34-61-25 | D00321B | | K01 | | D41369J | 17 | | *G | 001-099 |
| 5527 | 24 | | GK | | 5-3 | 34-61-25 | D00321B | | K01 | | D41369J | 17 | | *G | 115-199 |
| 5529 | 24 | | GK | | 2-11 | 24-28-11 | D00321E | | G11 | | D40904J | 3 | | *D | ALL |
| 5530 | 24 | | GK | | 3-8 | 24-28-11 | D00319E | | G11 | | D40904J | 3 | | *D | 001-099 |
| 5530 | 24 | | GK | | 3-7 | 24-28-11 | D00319E | | G11 | | D40904J | 3 | | *D | 115-199 |
| 5532 | 24 | | GK | | 5-0 | 24-28-11 | D00321E | | G10 | | D41369J | 13 | | *G | 001-099 |
| 5532 | 24 | | GK | | 5-2 | 24-28-11 | D00321E | | G10 | | D41369J | 13 | | *G | 115-199 |
| 5533 | 24 | | GK | | 3-8 | 24-28-11 | D00319E | | G10 | | D41369J | 13 | | *G | 001-099 |
| 5533 | 24 | | GK | | 3-10 | 24-28-11 | D00319E | | G10 | | D41369J | 13 | | *G | 115-199 |
| 5535 | 24 | | GK | | 4-2 | 24-28-11 | D00321E | | G09 | | D41317J | 17 | | *F | ALL |
| 5536 | 24 | | GK | | 2-9 | 24-28-11 | D00319E | | G09 | | D41317J | 17 | | *F | 001-099 |
| 5536 | 24 | | GK | | 2-10 | 24-28-11 | D00319E | | G09 | | D41317J | 17 | | *F | 115-199 |
| 5538 | 24 | | GK | | 2-11 | 24-28-11 | D00321E | | G12 | | D41451J | 26 | | *H | ALL |
| 5539 | 24 | | GK | | 3-8 | 24-28-11 | D00319E | | G12 | | D41451J | 26 | | *H | 001-099 |
| 5539 | 24 | | GK | | 3-7 | 24-28-11 | D00319E | | G12 | | D41451J | 26 | | *H | 115-199 |
| 5541 | 24 | | GK | | 3-8 | 24-28-11 | D00319E | | G08 | | D41451J | 27 | | | 001-099 |
| 5541 | 24 | | GK | | 3-7 | 24-28-11 | D00319E | | G08 | | D41451J | 27 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 125

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5542 | 24 | | GK | | 4-2 | 24-25-13 | D00321E | G08 | | | D41317J | 54 | | | 001-099 |
| 5542 | 24 | | GK | | 4-2 | 24-25-13 | D00321E | CAP | Y | | D41317J | 54 | | | 115-199 |
| 5543 | 22 | | GA | | 2-8 | 29-32-31 | D41844J | 14 | | | TB0207Y | A032 | BJ | | 001, 003-099 |
| 5543 | 22 | | GA | | 2-9 | 29-32-31 | D41844J | 14 | | | TB0207Y | A032 | BJ | | 002 |
| 5543 | 22 | | GA | | 2-6 | 29-32-31 | D41844J | 14 | | | TB0207Y | A032 | BJ | | 115-199 |
| 5544 | 22 | | GA | | 2-5 | 29-32-31 | D40684J | 7 | | | TB0207Y | A032 | BJ | | 001, 003-099, 115-199 |
| 5544 | 22 | | GA | | 2-6 | 29-32-31 | D40684J | 7 | | | TB0207Y | A032 | BJ | | 002 |
| 5545 | 24 | | GK | | 3-6 | 73-21-22 | D00319D | E13 | | | D41788J | 24 | | * | 001-099 |
| 5545 | 24 | | GK | | 4-5 | 73-21-22 | D00319D | E13 | | | D41788J | 24 | | *1 | 115-199 |
| 5546 | 24 | | GK | | 4-10 | 73-21-22 | D00321D | E13 | | | D41788J | 24 | | * | 001-099 |
| 5546 | 24 | | GK | | 3-4 | 73-21-22 | D00321D | E13 | | | D41788J | 24 | | *1 | 115-199 |
| 5550 | 24 | | GK | | 2-5 | 29-35-11 | D41879J | 28 | | | TB0207Y | A056 | BJ | | 001-099 |
| 5550 | 24 | | GK | | 2-7 | 29-35-11 | D41879J | 28 | | | TB0207Y | A056 | BJ | | 115-199 |
| 5551 | 24 | | GK | | 2-5 | 29-35-11 | D41879J | 30 | | | TB0207Y | A056 | BJ | | 001-099 |
| 5551 | 24 | | GK | | 2-7 | 29-35-11 | D41879J | 30 | | | TB0207Y | A056 | BJ | | 115-199 |
| 5552 | 24 | | GK | | 2-8 | 29-33-11 | D41058J | 28 | | | TB0207Y | C063 | BJ | | 001, 003-099 |
| 5552 | 24 | | GK | | 2-9 | 29-33-11 | D41058J | 28 | | | TB0207Y | C063 | BJ | | 002 |
| 5552 | 24 | | GK | | 2-10 | 29-33-11 | D41058J | 28 | | | TB0207Y | C063 | BJ | | 115-199 |
| 5553 | 24 | | GK | | 3-5 | 29-33-11 | D40584J | 28 | | | TB0207Y | C064 | BJ | | 001, 003-099 |
| 5553 | 24 | | GK | | 3-6 | 29-33-11 | D40584J | 28 | | | TB0207Y | C064 | BJ | | 002 |
| 5553 | 24 | | GK | | 3-7 | 29-33-11 | D40584J | 28 | | | TB0207Y | C064 | BJ | | 115-199 |
| 5554 | 24 | | GK | | 3-6 | 29-33-11 | D41844J | 24 | | | TB0207Y | C065 | BJ | | 001, 003-099 |
| 5554 | 24 | | GK | | 3-7 | 29-33-11 | D41844J | 24 | | | TB0207Y | C065 | BJ | | 002 |
| 5554 | 24 | | GK | | 3-4 | 29-33-11 | D41844J | 32 | | | TB0207Y | C065 | BJ | | 115-199 |
| 5555 | 24 | | GK | | 4-4 | 29-32-31 | D00321B | K08 | | | TB0207Y | A032 | BJ | | 001, 003-099 |
| 5555 | 24 | | GK | | 4-5 | 29-32-31 | D00321B | K08 | | | TB0207Y | A032 | BJ | | 002, 115-199 |
| 5556 | 24 | | GK | | 2-11 | 29-32-31 | D00319B | K08 | | | TB0207Y | A032 | BJ | | 001, 003-099 |
| 5556 | 24 | | GK | | 3-1 | 29-32-31 | D00319B | K08 | | | TB0207Y | A032 | BJ | | 002 |
| 5556 | 24 | | GK | | 3-0 | 29-32-31 | D00319B | K08 | | | TB0207Y | A032 | BJ | | 115-199 |
| 5557 | 22 | | GA | | 2-8 | 29-32-31 | D41844J | 15 | | | TB0207Y | C032 | BJ | | 001, 003-099 |
| 5557 | 22 | | GA | | 2-9 | 29-32-31 | D41844J | 15 | | | TB0207Y | C032 | BJ | | 002 |
| 5557 | 22 | | GA | | 2-6 | 29-32-31 | D41844J | 15 | | | TB0207Y | C032 | BJ | | 115-199 |
| 5558 | 24 | | GK | | 3-1 | 29-32-31 | D00319A | K03 | | | TB0207Y | C032 | BJ | | 001, 003-099, 115-199 |
| 5558 | 24 | | GK | | 3-2 | 29-32-31 | D00319A | K03 | | | TB0207Y | C032 | BJ | | 002 |
| 5559 | 24 | | GK | | 4-6 | 29-32-31 | D00321A | K03 | | | TB0207Y | C032 | BJ | | 001, 003-099, 115-199 |
| 5559 | 24 | | GK | | 4-7 | 29-32-31 | D00321A | K03 | | | TB0207Y | C032 | BJ | | 002 |
| 5560 | 22 | | GA | | 3-4 | 29-32-31 | D40704J | 6 | | | TB0207Y | C032 | BJ | | 001, 003-099, 115-199 |
| 5560 | 22 | | GA | | 3-5 | 29-32-31 | D40704J | 6 | | | TB0207Y | C032 | BJ | | 002 |
| 5562 | 24 | | GK | | 3-10 | 27-51-41 | D00321D | B14 | | | D41698J | 3 | | *M | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 126

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5563 | 24 | | GK | | 2-11 | 27-51-41 | D00319D | | B14 | | D41698J | 3 | | *M | ALL |
| 5565 | 24 | | GK | | 3-9 | 27-51-41 | D00321E | | D01 | | D41698J | 4 | | *M | 001-099 |
| 5565 | 24 | | GK | | 3-8 | 27-51-41 | D00321E | | D01 | | D41698J | 4 | | *M | 115-199 |
| 5566 | 24 | | GK | | 2-10 | 27-51-41 | D00319E | | D01 | | D41698J | 4 | | *M | 001-099 |
| 5566 | 24 | | GK | | 2-9 | 27-51-41 | D00319E | | D01 | | D41698J | 4 | | *M | 115-199 |
| 5568 | 24 | | GK | | 2-10 | 27-51-41 | D00319E | | B01 | | D41698J | 1 | | *M | 001-099 |
| 5568 | 24 | | GK | | 2-9 | 27-51-41 | D00319E | | B01 | | D41698J | 1 | | *M | 115-199 |
| 5569 | 24 | | GK | | 3-9 | 27-51-41 | D00321E | | B01 | | D41698J | 1 | | *M | 001-099 |
| 5569 | 24 | | GK | | 3-8 | 27-51-41 | D00321E | | B01 | | D41698J | 1 | | *M | 115-199 |
| 5571 | 24 | | GK | | 2-11 | 27-51-41 | D00319D | | G15 | | D41698J | 2 | | *M | ALL |
| 5572 | 24 | | GK | | 3-10 | 27-51-41 | D00321D | | G15 | | D41698J | 2 | | *M | ALL |
| 5574 | 24 | | GK | | 2-7 | 49-94-14 | D00319F | | F10 | | D41660J | 14 | | *K | 115-199 |
| 5576 | 24 | | GK | | 3-11 | 29-35-11 | D41774J | | 24 | | TB0207Y | C056 | BJ | | 115-199 |
| 5577 | 24 | | GK | | 3-11 | 49-94-14 | D00321F | | F10 | | D41660J | 14 | | *K | 115-199 |
| 5578 | 24 | | GK | | 2-7 | 29-35-11 | D41720J | | 18 | | TB0207Y | C056 | BJ | | 001, 003-099 |
| 5578 | 24 | | GK | | 2-8 | 29-35-11 | D41720J | | 18 | | TB0207Y | C056 | BJ | | 002 |
| 5578 | 24 | | GK | | 2-9 | 29-35-11 | D41720J | | 18 | | TB0207Y | C056 | BJ | | 115-199 |
| 5579 | 22 | | GA | | 2-9 | 49-94-14 | D41660J | | 13 | | GD02204 | DC.. | 2 | | 115-199 |
| 5581 | 22 | | GA | | 3-2 | 49-94-14 | D41660J | | 16 | | TB0207Z | 77 | BJ | | 115-199 |
| 5583 | 24 | | GK | | 2-8 | 36-11-21 | D00319E | | K06 | | D41058J | 17 | | *E | 001-099 |
| 5583 | 24 | | GK | | 2-9 | 36-11-21 | D00319E | | K06 | | D41058J | 17 | | *E | 115-199 |
| 5584 | 24 | | GK | | 4-0 | 36-11-21 | D00321E | | K06 | | D41058J | 17 | | *E | 001-099 |
| 5584 | 24 | | GK | | 4-1 | 36-11-21 | D00321E | | K06 | | D41058J | 17 | | *E | 115-199 |
| 5586 | 24 | | GK | | 3-11 | 36-11-11 | D00319E | | K03 | | D40584J | 27 | | *C | 001-099 |
| 5586 | 24 | | GK | | 2-7 | 36-11-11 | D00319E | | K03 | | D41879J | 17 | | *Z | 115-199 |
| 5587 | 24 | | GK | | 2-9 | 36-11-11 | D00321E | | K03 | | D40584J | 27 | | *C | 001-099 |
| 5587 | 24 | | GK | | 3-11 | 36-11-11 | D00321E | | K03 | | D41879J | 17 | | *Z | 115-199 |
| 5588 | 24 | | GK | | 2-7 | 36-11-12 | D40584J | | 36 | | TB0207Y | A089 | BJ | | 001, 003-099 |
| 5588 | 24 | | GK | | 2-8 | 36-11-12 | D40584J | | 36 | | TB0207Y | A089 | BJ | | 002 |
| 5588 | 24 | | GK | | 2-9 | 36-11-12 | D40584J | | 36 | | TB0207Y | A089 | BJ | | 115-199 |
| 5589 | 24 | | GK | | 2-7 | 36-11-12 | D00321E | | K07 | | TB0207Y | A089 | BJ | | 001-099 |
| 5589 | 24 | | GK | | 2-8 | 36-11-12 | D00321E | | K07 | | TB0207Y | A089 | BJ | | 115-199 |
| 5590 | 24 | | GK | | 3-2 | 36-11-12 | D00319E | | K07 | | TB0207Y | A089 | BJ | | 001, 003-099, 115-199 |
| 5590 | 24 | | GK | | 3-3 | 36-11-12 | D00319E | | K07 | | TB0207Y | A089 | BJ | | 002 |
| 5592 | 24 | | GK | | 4-0 | 36-11-22 | D00321E | | K11 | | D41058J | 3 | | *E | 001-099 |
| 5592 | 24 | | GK | | 4-1 | 36-11-22 | D00321E | | K11 | | D41058J | 3 | | *E | 115-199 |
| 5593 | 24 | | GK | | 2-8 | 36-11-22 | D00319E | | K11 | | D41058J | 3 | | *E | 001-099 |
| 5593 | 24 | | GK | | 2-9 | 36-11-22 | D00319E | | K11 | | D41058J | 3 | | *E | 115-199 |
| 5594 | 24 | | GK | | 2-7 | 36-11-12 | D40584J | | 42 | | TB0207Y | A089 | BJ | | 001, 003-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 127

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | |
| 5594 | 24 | GK | | | 2-8 | 36-11-12 | D40584J | | 42 | | TB0207Y | A089 | BJ | | 002 |
| 5594 | 24 | GK | | | 2-9 | 36-11-12 | D40584J | | 42 | | TB0207Y | A089 | BJ | | 115-199 |
| 5597 | 24 | GK | | | 3-11 | 36-22-11 | D42086J | | 28 | | TB0207Y | C091 | BJ | | 115-199 |
| 5598 | 24 | GK | | | 3-6 | 36-22-11 | D41058J | | 5 | | TB0207Y | C091 | BJ | | 115-199 |
| 5599 | 24 | GK | | | 2-6 | 36-22-11 | D00319E | | K02 | | D42086J | 28 | | *1 | 001-099 |
| 5599 | 24 | GK | | | 3-2 | 36-22-11 | D00319E | | K02 | | TB0207Y | C091 | BJ | | 115-199 |
| 5601 | 24 | GK | | | 3-11 | 36-22-11 | D00321E | | K02 | | D42086J | 28 | | *1 | 001-099 |
| 5601 | 24 | GK | | | 2-8 | 36-22-11 | D00321E | | K02 | | TB0207Y | C091 | BJ | | 115-199 |
| 5602 | 24 | GK | | | 3-1 | 36-22-11 | D41664J | | 10 | | TB0207Y | A092 | BJ | | ALL |
| 5603 | 24 | GK | | | 2-8 | 36-22-11 | D40584J | | 39 | | TB0207Y | A092 | BJ | | 001-099 |
| 5603 | 24 | GK | | | 2-9 | 36-22-11 | D40584J | | 39 | | TB0207Y | A092 | BJ | | 115-199 |
| 5604 | 24 | GK | | | 3-2 | 36-22-11 | D00319E | | K10 | | TB0207Y | A092 | BJ | | 001, 003-099, 115-199 |
| 5604 | 24 | GK | | | 3-3 | 36-22-11 | D00319E | | K10 | | TB0207Y | A092 | BJ | | 002 |
| 5605 | 24 | GK | | | 2-7 | 36-22-11 | D00321E | | K10 | | TB0207Y | A092 | BJ | | 001-099 |
| 5605 | 24 | GK | | | 2-8 | 36-22-11 | D00321E | | K10 | | TB0207Y | A092 | BJ | | 115-199 |
| 5606 | 24 | GK | | | 4-5 | 24-27-11 | D40584J | | 33 | | TB0207Y | A033 | BJ | | ALL |
| 5607 | 24 | GK | | | 4-6 | 24-27-11 | D00321D | | B03 | | TB0207Y | A033 | BJ | | 001-099 |
| 5607 | 24 | GK | | | 4-5 | 24-27-11 | D00321D | | B03 | | TB0207Y | A033 | BJ | | 115-199 |
| 5608 | 24 | GK | | | 4-2 | 24-27-11 | D41451J | | 25 | | TB0207Y | A033 | BJ | | ALL |
| 5609 | 24 | GK | | | 3-1 | 24-27-11 | D00319D | | B03 | | TB0207Y | A033 | BJ | | ALL |
| 5610 | 22 | GA | | | 4-5 | 24-27-11 | D40584J | | 34 | | TB0207Y | C033 | BJ | | ALL |
| 5611 | 24 | GK | | | 4-6 | 24-27-11 | D00321D | | B01 | | TB0207Y | C033 | BJ | | 001-099 |
| 5611 | 24 | GK | | | 4-5 | 24-27-11 | D00321D | | B01 | | TB0207Y | C033 | BJ | | 115-199 |
| 5612 | 22 | GA | | | 4-2 | 24-27-11 | D41451J | | 24 | | TB0207Y | C033 | BJ | | ALL |
| 5613 | 24 | GK | | | 3-1 | 24-27-11 | D00319D | | B01 | | TB0207Y | C033 | BJ | | ALL |
| 5614 | 22 | GA | | | 3-11 | 24-27-11 | D40584J | | 51 | | TB0207Y | A037 | BJ | | 001-099 |
| 5614 | 22 | GA | | | 4-0 | 24-27-11 | D40584J | | 51 | | TB0207Y | A037 | BJ | | 115-199 |
| 5615 | 24 | GK | | | 3-11 | 24-27-11 | D00321D | | C06 | | TB0207Y | A037 | BJ | | 001, 003-099 |
| 5615 | 24 | GK | | | 4-0 | 24-27-11 | D00321D | | C06 | | TB0207Y | A037 | BJ | | 002, 115-199 |
| 5616 | 22 | GA | | | 3-8 | 24-27-11 | D41451J | | 23 | | TB0207Y | A037 | BJ | | ALL |
| 5617 | 24 | GK | | | 2-7 | 24-27-11 | D00319D | | C06 | | TB0207Y | A037 | BJ | | 001-099 |
| 5617 | 24 | GK | | | 2-8 | 24-27-11 | D00319D | | C06 | | TB0207Y | A037 | BJ | | 115-199 |
| 5618 | 22 | GA | | | 2-3 | 24-27-21 | D41058J | | 1 | | TB0207Y | A038 | BJ | | 001, 003-099, 115-199 |
| 5618 | 22 | GA | | | 2-4 | 24-27-21 | D41058J | | 1 | | TB0207Y | A038 | BJ | | 002 |
| 5619 | 24 | GK | | | 3-11 | 24-27-21 | D00321D | | A12 | | TB0207Y | C037 | BJ | | 001, 003-099 |
| 5619 | 24 | GK | | | 4-0 | 24-27-21 | D00321D | | A12 | | TB0207Y | C037 | BJ | | 002, 115-199 |
| 5620 | 22 | GA | | | 3-5 | 24-27-21 | D40892J | | 6 | | TB0207Y | A038 | BJ | | ALL |
| 5621 | 24 | GK | | | 2-7 | 24-27-21 | D00319D | | A12 | | TB0207Y | C037 | BJ | | 001-099 |
| 5621 | 24 | GK | | | 2-8 | 24-27-21 | D00319D | | A12 | | TB0207Y | C037 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 128

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5622 | 22 | | GA | | 2-3 | 24-27-21 | D41058J | | 2 | | TB0207Y | C037 | BJ | | 001, 003-099, 115-199 |
| 5622 | 22 | | GA | | 2-4 | 24-27-21 | D41058J | | 2 | | TB0207Y | C037 | BJ | | 002 |
| 5623 | 24 | | GK | | 3-11 | 24-27-21 | D00321D | | B02 | | TB0207Y | A038 | BJ | | 001, 003-099 |
| 5623 | 24 | | GK | | 4-0 | 24-27-21 | D00321D | | B02 | | TB0207Y | A038 | BJ | | 002, 115-199 |
| 5624 | 22 | | GA | | 3-5 | 24-27-21 | D40892J | | 5 | | TB0207Y | C037 | BJ | | ALL |
| 5625 | 24 | | GK | | 2-7 | 24-27-21 | D00319D | | B02 | | TB0207Y | A038 | BJ | | 001-099 |
| 5625 | 24 | | GK | | 2-8 | 24-27-21 | D00319D | | B02 | | TB0207Y | A038 | BJ | | 115-199 |
| 5626 | 22 | | GA | | 2-3 | 24-27-21 | D41058J | | 21 | | TB0207Y | C038 | BJ | | 001, 003-099, 115-199 |
| 5626 | 22 | | GA | | 2-4 | 24-27-21 | D41058J | | 21 | | TB0207Y | C038 | BJ | | 002 |
| 5627 | 24 | | GK | | 3-11 | 24-27-21 | D00321D | | C01 | | TB0207Y | C038 | BJ | | 001, 003-099 |
| 5627 | 24 | | GK | | 4-0 | 24-27-21 | D00321D | | C01 | | TB0207Y | C038 | BJ | | 002, 115-199 |
| 5628 | 22 | | GA | | 3-5 | 24-27-21 | D40892J | | 4 | | TB0207Y | C038 | BJ | | ALL |
| 5629 | 24 | | GK | | 2-7 | 24-27-21 | D00319D | | C01 | | TB0207Y | C038 | BJ | | 001-099 |
| 5629 | 24 | | GK | | 2-8 | 24-27-21 | D00319D | | C01 | | TB0207Y | C038 | BJ | | 115-199 |
| 5631 | 24 | | GK | | 3-6 | 24-27-41 | D00319D | | C07 | | D40602J | 6 | | *1 | 001-099 |
| 5631 | 24 | | GK | | 3-5 | 24-27-41 | D00319D | | C07 | | D40602J | 6 | | *1 | 115-199 |
| 5632 | 24 | | GK | | 4-10 | 24-27-41 | D00321D | | C07 | | D40602J | 6 | | *1 | 001-099 |
| 5632 | 24 | | GK | | 4-9 | 24-27-41 | D00321D | | C07 | | D40602J | 6 | | *1 | 115-199 |
| 5634 | 24 | | GK | | 3-8 | 24-33-11 | D00319A | | D04 | | D41844J | 2 | | *X | 001-099 |
| 5634 | 24 | | GK | | 3-5 | 24-33-11 | D00319A | | D04 | | D41844J | 2 | | *X | 115-199 |
| 5635 | 24 | | GK | | 5-1 | 24-33-11 | D00321A | | D04 | | D41844J | 2 | | *X | 001-099 |
| 5635 | 24 | | GK | | 4-10 | 24-33-11 | D00321A | | D04 | | D41844J | 2 | | *X | 115-199 |
| 5637 | 24 | | GK | | 3-7 | 24-33-11 | D00319D | | B04 | | D41844J | 1 | | *X | 001-099 |
| 5637 | 24 | | GK | | 3-5 | 24-33-11 | D00319D | | B04 | | D41844J | 1 | | *X | 115-199 |
| 5638 | 24 | | GK | | 5-0 | 24-33-11 | D00321D | | B04 | | D41844J | 1 | | *X | 001-099 |
| 5638 | 24 | | GK | | 4-9 | 24-33-11 | D00321D | | B04 | | D41844J | 1 | | *X | 115-199 |
| 5640 | 24 | | GK | | 3-5 | 24-34-11 | D00319E | | G14 | | D40892J | 7 | | *1 | 001-099 |
| 5640 | 24 | | GK | | 3-4 | 24-34-11 | D00319E | | G14 | | D40892J | 7 | | *1 | 115-199 |
| 5641 | 24 | | GK | | 2-8 | 24-34-11 | D00321E | | G14 | | D40892J | 7 | | *1 | ALL |
| 5643 | 24 | | GK | | 3-4 | 24-34-11 | D00319B | | E01 | | D40892J | 8 | | *1 | ALL |
| 5644 | 24 | | GK | | 2-9 | 24-34-11 | D00321B | | E01 | | D40892J | 8 | | *1 | ALL |
| 5646 | 24 | | GK | | 2-11 | 24-34-11 | D00321E | | A12 | | D40904J | 2 | | *D | ALL |
| 5647 | 24 | | GK | | 3-8 | 24-34-11 | D00319E | | A12 | | D40904J | 2 | | *D | 001-099 |
| 5647 | 24 | | GK | | 3-7 | 24-34-11 | D00319E | | A12 | | D40904J | 2 | | *D | 115-199 |
| 5649 | 24 | | GK | | 2-9 | 24-34-11 | D00321F | | A04 | | D40904J | 1 | | *D | ALL |
| 5650 | 24 | | GK | | 3-6 | 24-34-11 | D00319F | | A04 | | D40904J | 1 | | *D | ALL |
| 5652 | 24 | | GK | | 2-11 | 24-34-11 | D00321E | | J14 | | D40904J | 5 | | *D | ALL |
| 5653 | 24 | | GK | | 3-8 | 24-34-11 | D00319E | | J14 | | D40904J | 5 | | *D | 001-099 |
| 5653 | 24 | | GK | | 3-7 | 24-34-11 | D00319E | | J14 | | D40904J | 5 | | *D | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 129

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5658 | 24 | | GK | | 2-7 | 24-34-11 | D00319E | C15 | | | D42185J | 9 | | *O | 001-099 |
| 5658 | 24 | | GK | | 2-8 | 24-34-11 | D00319E | C15 | | | D42185J | 9 | | *1 | 115-199 |
| 5659 | 24 | | GK | | 3-6 | 24-34-11 | D00321E | C15 | | | D42185J | 9 | | *O | 001-099 |
| 5659 | 24 | | GK | | 3-7 | 24-34-11 | D00321E | C15 | | | D42185J | 9 | | *1 | 115-199 |
| 5661 | 24 | | GK | | 2-6 | 24-34-11 | D00319F | A03 | | | D41660J | 11 | | | 001-099 |
| 5661 | 24 | | GK | | 2-7 | 24-34-11 | D00319F | A03 | | | D41660J | 11 | | | 115-199 |
| 5662 | 24 | | GK | | 4-0 | 24-25-13 | D00321F | A03 | | | D41317J | 53 | | | 001-099 |
| 5662 | 24 | | GK | | 4-1 | 24-25-13 | D00321F | CAP | Y | | D41317J | 53 | | | 115-199 |
| 5664 | 24 | | GK | | 2-9 | 24-51-14 | D00321A | E05 | | | D40584J | 43 | | *C | ALL |
| 5665 | 24 | | GK | | 3-11 | 24-51-14 | D00319A | E05 | | | D40584J | 43 | | *C | 001-099 |
| 5665 | 24 | | GK | | 4-0 | 24-51-14 | D00319A | E05 | | | D40584J | 43 | | *C | 115-199 |
| 5667 | 24 | | GK | | 4-2 | 24-51-24 | D00321D | C08 | | | D41058J | 4 | | *E | ALL |
| 5668 | 24 | | GK | | 2-9 | 24-51-24 | D00319D | C08 | | | D41058J | 4 | | *E | 001-099 |
| 5668 | 24 | | GK | | 2-10 | 24-51-24 | D00319D | C08 | | | D41058J | 4 | | *E | 115-199 |
| 5675 | 24 | | GK | | 4-9 | 30-11-11 | D00321F | J02 | | | D41844J | 19 | | *X | 001-099 |
| 5675 | 24 | | GK | | 2-11 | 30-11-11 | D00321F | J02 | | | D41842J | 2 | | *1 | 115-199 |
| 5676 | 24 | | GK | | 4-9 | 30-11-11 | D00321F | G07 | | | D41844J | 20 | | *X | 001-099 |
| 5676 | 24 | | GK | | 2-11 | 30-11-11 | D00321F | G07 | | | D41842J | 1 | | *1 | 115-199 |
| 5677 | 24 | | GK | | 3-4 | 30-11-11 | D00319F | G07 | | | D41844J | 20 | | *X | 001-099 |
| 5677 | 24 | | GK | | 4-1 | 30-11-11 | D00319F | G07 | | | D41842J | 1 | | *1 | 115-199 |
| 5678 | 24 | | GK | | 3-4 | 30-11-11 | D00319F | J02 | | | D41844J | 19 | | *X | 001-099 |
| 5678 | 24 | | GK | | 4-1 | 30-11-11 | D00319F | J02 | | | D41842J | 2 | | *1 | 115-199 |
| 5682 | 22 | | GA | | 3-5 | 79-33-11 | D42023J | 18 | | | TB0207Y | C011 | BJ | | 001, 003-099, 115-199 |
| 5682 | 22 | | GA | | 3-6 | 79-33-11 | D42023J | 18 | | | TB0207Y | C011 | BJ | | 002 |
| 5683 | 22 | | GA | | 2-7 | 79-33-11 | D42041J | 18 | | | TB0207Y | A011 | BJ | | 001, 003-099 |
| 5683 | 22 | | GA | | 2-8 | 79-33-11 | D42041J | 18 | | | TB0207Y | A011 | BJ | | 002 |
| 5683 | 22 | | GA | | 2-6 | 79-33-11 | D42041J | 18 | | | TB0207Y | A011 | BJ | | 115-199 |
| 5685 | 24 | | GK | | 2-11 | 32-09-11 | D00319B | H01 | | | D41632J | 3 | | *1 | 001-099 |
| 5685 | 24 | | GK | | 3-0 | 32-09-11 | D00319B | H01 | | | D41632J | 3 | | *1 | 115-199 |
| 5686 | 24 | | GK | | 3-4 | 32-09-11 | D00321B | H01 | | | D41632J | 3 | | *1 | ALL |
| 5688 | 24 | | GK | | 2-11 | 32-09-11 | D00319F | E09 | | | D41632J | 4 | | *1 | 001-099 |
| 5688 | 24 | | GK | | 2-10 | 32-09-11 | D00319F | E09 | | | D41632J | 4 | | *1 | 115-199 |
| 5689 | 24 | | GK | | 3-2 | 32-09-11 | D00321F | E09 | | | D41632J | 4 | | *1 | ALL |
| 5691 | 24 | | GK | | 3-11 | 32-09-12 | D00319B | J13 | | | D41794J | 3 | | *1 | 001-099 |
| 5691 | 24 | | GK | | 4-0 | 32-09-12 | D00319B | J13 | | | D41794J | 3 | | *1 | 115-199 |
| 5692 | 24 | | GK | | 5-3 | 32-09-12 | D00321B | J13 | | | D41794J | 3 | | *1 | 001-099 |
| 5692 | 24 | | GK | | 5-5 | 32-09-12 | D00321B | J13 | | | D41794J | 3 | | *1 | 115-199 |
| 5694 | 24 | | GK | | 3-8 | 32-09-12 | D00319F | F08 | | | D41794J | 2 | | *1 | 001-099 |
| 5694 | 24 | | GK | | 3-11 | 32-09-12 | D00319F | F08 | | | D41794J | 2 | | *1 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 130

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5695 | 24 | | GK | | 5-1 | 32-09-12 | D00321F | | F08 | | D41794J | 2 | | *1 | 001-099 |
| 5695 | 24 | | GK | | 5-3 | 32-09-12 | D00321F | | F08 | | D41794J | 2 | | *1 | 115-199 |
| 5698 | 24 | | GK | | 3-9 | 22-21-11 | D00319D | | A06 | | D41451J | 40 | | *H | 001-099 |
| 5698 | 24 | | GK | | 3-8 | 22-21-11 | D00319D | | A06 | | D41451J | 40 | | *H | 115-199 |
| 5699 | 24 | | GK | | 3-0 | 22-21-11 | D00321D | | A06 | | D41451J | 40 | | *H | ALL |
| 5714 | 24 | | GK | | 5-1 | 29-21-32 | D00321F | | K10 | | D42041J | 17 | | *Y | 001-099 |
| 5714 | 24 | | GK | | 5-1 | 29-21-32 | D00321F | | K10 | | D42041J | 17 | | *1 | 115-199 |
| 5715 | 24 | | GK | | 3-8 | 29-21-32 | D00319F | | K10 | | D42041J | 17 | | *Y | 001-099 |
| 5715 | 24 | | GK | | 3-9 | 29-21-32 | D00319F | | K10 | | D42041J | 17 | | *1 | 115-199 |
| 5716 | 24 | | GK | | 0-7 | 32-61-12 | D41867J | | 23 | | D41867J | 11 | | | 115-199 |
| 5717 | 24 | | GK | | 4-1 | 21-58-12 | D00319E | | D14 | | D41738J | 5 | | *R | 001-099 |
| 5717 | 24 | | GK | | 4-2 | 21-58-12 | D00319E | | D14 | | D41738J | 5 | | *R | 115-199 |
| 5718 | 24 | | GK | | 3-2 | 29-35-11 | D00321F | | J03 | | D41720J | 19 | | *N | ALL |
| 5719 | 24 | | GK | | 2-11 | 29-35-11 | D00319F | | J03 | | D41720J | 19 | | *N | 001-099 |
| 5719 | 24 | | GK | | 2-10 | 29-35-11 | D00319F | | J03 | | D41720J | 19 | | *N | 115-199 |
| 5720 | 24 | | GK | | 4-3 | 21-58-12 | D00319D | | A02 | | D41738J | 51 | | *R | ALL |
| 5721 | 24 | | GK | | 5-2 | 29-35-11 | D00321F | | G06 | | D41792J | 5 | | *1 | 001-099 |
| 5721 | 24 | | GK | | 5-4 | 29-35-11 | D00321F | | G06 | | D41792J | 5 | | *1 | 115-199 |
| 5722 | 24 | | GK | | 3-10 | 29-35-11 | D00319F | | G06 | | D41792J | 5 | | *1 | 001-099 |
| 5722 | 24 | | GK | | 4-1 | 29-35-11 | D00319F | | G06 | | D41792J | 5 | | *1 | 115-199 |
| 5723 | 24 | | GK | | 4-3 | 21-58-12 | D00319D | | F13 | | D41738J | 52 | | *R | ALL |
| 5724 | 24 | | GK | | 3-9 | 29-35-11 | D00321F | | K03 | | D41879J | 15 | | *Z | 001-099 |
| 5724 | 24 | | GK | | 3-10 | 29-35-11 | D00321F | | K03 | | D41879J | 15 | | *Z | 115-199 |
| 5725 | 24 | | GK | | 2-5 | 29-35-11 | D00319F | | K03 | | D41879J | 15 | | *Z | 001-099 |
| 5725 | 24 | | GK | | 2-6 | 29-35-11 | D00319F | | K03 | | D41879J | 15 | | *Z | 115-199 |
| 5726 | 24 | | GK | | 3-0 | 21-58-12 | D00321E | | D14 | | D41738J | 5 | | *R | 001-099 |
| 5726 | 24 | | GK | | 3-1 | 21-58-12 | D00321E | | D14 | | D41738J | 5 | | *R | 115-199 |
| 5727 | 24 | | GK | | 3-0 | 27-31-11 | D00321D | | C04 | | D41451J | 50 | | *H | ALL |
| 5728 | 24 | | GK | | 3-9 | 27-31-11 | D00319D | | C04 | | D41451J | 50 | | *H | 001-099 |
| 5728 | 24 | | GK | | 3-8 | 27-31-11 | D00319D | | C04 | | D41451J | 50 | | *H | 115-199 |
| 5729 | 24 | | GK | | 3-1 | 21-58-12 | D00321D | | A02 | | D41738J | 51 | | *R | 001-099 |
| 5729 | 24 | | GK | | 3-2 | 21-58-12 | D00321D | | A02 | | D41738J | 51 | | *R | 115-199 |
| 5730 | 24 | | GK | | 2-11 | 73-34-11 | D00321E | | J03 | | D41774J | 2 | | *U | 001-099 |
| 5730 | 24 | | GK | | 3-0 | 73-34-11 | D00321E | | J03 | | D41774J | 2 | | *U | 115-199 |
| 5731 | 24 | | GK | | 3-8 | 73-34-11 | D00319E | | J03 | | D41774J | 2 | | *U | 001-099 |
| 5731 | 24 | | GK | | 4-2 | 73-34-11 | D00319E | | J03 | | D41774J | 2 | | *U | 115-199 |
| 5732 | 24 | | GK | | 3-1 | 21-58-12 | D00321D | | F13 | | D41738J | 52 | | *R | 001-099 |
| 5732 | 24 | | GK | | 3-2 | 21-58-12 | D00321D | | F13 | | D41738J | 52 | | *R | 115-199 |
| 5733 | 24 | | GK | | 3-7 | 73-34-11 | D00321B | | H05 | | D41764J | 2 | | *S | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 131

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|----|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | | | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | |
| 5733 | 24 | | GK | | 4-10 | 73-34-11 | D00321B | H05 | | | D41764J | 2 | | *S | 115-199 |
| 5734 | 24 | | GK | | 2-7 | 73-34-11 | D00319B | H05 | | | D41764J | 2 | | *S | 001-099 |
| 5734 | 24 | | GK | | 3-5 | 73-34-11 | D00319B | H05 | | | D41764J | 2 | | *S | 115-199 |
| 5735 | 24 | | GK | | 2-10 | 30-31-11 | D00319E | C03 | | | D41698J | 21 | | *M | 001-099 |
| 5735 | 24 | | GK | | 2-9 | 30-31-11 | D00319E | C03 | | | D41698J | 21 | | *M | 115-199 |
| 5736 | 24 | | GK | | 2-11 | 30-31-11 | D00319A | D01 | | | D41698J | 22 | | *M | ALL |
| 5738 | 24 | | GK | | 2-6 | 76-11-12 | D41776J | 32 | | | TB0207Y | C083 | BJ | | 115-199 |
| 5739 | 24 | | GK | | 3-0 | 76-11-11 | D41738J | 44 | | | TB0207Y | C100 | BJ | | 115-199 |
| 5741 | 24 | | GK | | 3-11 | 21-51-15 | D00319A | D08 | | | D40584J | 9 | | *C | 001-099 |
| 5741 | 24 | | GK | | 4-0 | 21-51-15 | D00319A | D08 | | | D40584J | 9 | | *C | 115-199 |
| 5742 | 24 | | GK | | 2-9 | 21-51-15 | D00321A | D08 | | | D40584J | 9 | | *C | ALL |
| 5744 | 24 | | GK | | 3-11 | 21-51-15 | D00319A | E06 | | | D40584J | 10 | | *C | 001-099 |
| 5744 | 24 | | GK | | 4-0 | 21-51-15 | D00319A | E06 | | | D40584J | 10 | | *C | 115-199 |
| 5745 | 24 | | GK | | 2-9 | 21-51-15 | D00321A | E06 | | | D40584J | 10 | | *C | ALL |
| 5747 | 24 | | GK | | 2-8 | 21-51-15 | D00319F | D02 | | | D41664J | 2 | | *L | ALL |
| 5748 | 24 | | GK | | 3-7 | 21-51-15 | D00321F | D02 | | | D41664J | 2 | | *L | ALL |
| 5750 | 24 | | GK | | 2-10 | 21-51-25 | D00319A | G10 | | | D41058J | 9 | | *E | ALL |
| 5751 | 24 | | GK | | 4-3 | 21-51-25 | D00321A | G10 | | | D41058J | 9 | | *E | ALL |
| 5753 | 24 | | GK | | 2-10 | 21-51-25 | D00319A | D05 | | | D41058J | 10 | | *E | ALL |
| 5754 | 24 | | GK | | 4-3 | 21-51-25 | D00321A | D05 | | | D41058J | 10 | | *E | ALL |
| 5756 | 24 | | GK | | 2-8 | 21-51-25 | D00319D | F11 | | | D42086J | 31 | | *1 | 001-099 |
| 5756 | 24 | | GK | | 3-3 | 21-51-25 | D00319D | F11 | | | D42086J | 31 | | *1 | 115-199 |
| 5757 | 24 | | GK | | 4-0 | 21-51-25 | D00321D | F11 | | | D42086J | 31 | | *1 | 001-099 |
| 5757 | 24 | | GK | | 4-7 | 21-51-25 | D00321D | F11 | | | D42086J | 31 | | *1 | 115-199 |
| 5759 | 24 | | GK | | 3-9 | 21-58-11 | D00319F | H07 | | | D40584J | 35 | | *C | ALL |
| 5760 | 24 | | GK | | 2-7 | 21-58-11 | D00321F | H07 | | | D40584J | 35 | | *C | 001-099 |
| 5760 | 24 | | GK | | 2-8 | 21-58-11 | D00321F | H07 | | | D40584J | 35 | | *C | 115-199 |
| 5765 | 24 | | GK | | 3-4 | 21-58-12 | D00319F | E08 | | | D41844J | 6 | | *X | 001-099 |
| 5765 | 24 | | GK | | 3-2 | 21-58-12 | D00319F | E08 | | | D41844J | 6 | | *X | 115-199 |
| 5766 | 24 | | GK | | 4-9 | 21-58-12 | D00321F | E08 | | | D41844J | 6 | | *X | 001-099 |
| 5766 | 24 | | GK | | 4-6 | 21-58-12 | D00321F | E08 | | | D41844J | 6 | | *X | 115-199 |
| 5768 | 24 | | GK | | 2-9 | 21-58-24 | D00319F | J07 | | | D41840J | 5 | | *W | 115-199 |
| 5769 | 24 | | GK | | 4-1 | 21-58-24 | D00321F | J07 | | | D41840J | 5 | | *W | 115-199 |
| 5771 | 24 | | GK | | 4-1 | 21-58-24 | D00321F | K07 | | | D41840J | 11 | | *W | 115-199 |
| 5772 | 24 | | GK | | 2-9 | 21-58-24 | D00319F | K07 | | | D41840J | 11 | | *W | 115-199 |
| 5774 | 24 | | GK | | 2-11 | 21-61-11 | D00319D | A14 | | | D41840J | 10 | | *W | 001-099 |
| 5774 | 24 | | GK | | 3-0 | 21-61-11 | D00319D | A14 | | | D41840J | 10 | | *W | 115-199 |
| 5775 | 24 | | GK | | 4-3 | 21-61-11 | D00321D | A14 | | | D41840J | 10 | | *W | ALL |
| 5777 | 24 | | GK | | 2-6 | 21-61-21 | D00319F | K09 | | | D41058J | 11 | | *E | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 132

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5777 | 24 | | GK | | 2-7 | 21-61-21 | D00319F | K09 | | | D41058J | 11 | | *E | 115-199 |
| 5778 | 24 | | GK | | 3-11 | 21-61-21 | D00321F | K09 | | | D41058J | 11 | | *E | ALL |
| 5780 | 24 | | GK | | 2-8 | 21-61-31 | D00319E | J10 | | | D41058J | 23 | | *E | 001-099 |
| 5780 | 24 | | GK | | 2-9 | 21-61-31 | D00319E | J10 | | | D41058J | 23 | | *E | 115-199 |
| 5781 | 24 | | GK | | 4-0 | 21-61-31 | D00321E | J10 | | | D41058J | 23 | | *E | 001-099 |
| 5781 | 24 | | GK | | 4-1 | 21-61-31 | D00321E | J10 | | | D41058J | 23 | | *E | 115-199 |
| 5796 | 24 | | GK | | 3-10 | 22-21-21 | D00319A | D07 | | | D41369J | 31 | | *G | 001-099 |
| 5796 | 24 | | G1 | IP | 4-0 | 22-21-21 | D00319A | D07 | | | D41369J | 31 | | *G | 115-199 |
| 5796Z | | | | IP | 0-0 | 22-21-21 | D00319A | DED | | | D41369J | DED | | | 115-199 |
| 5797 | 24 | | GK | | 5-2 | 22-21-21 | D00321A | D07 | | | D41369J | 31 | | *G | 001-099 |
| 5797 | 24 | | G1 | IF | 5-4 | 22-21-21 | D00321A | D07 | | | D41369J | 31 | | *G | 115-199 |
| 5797Z | | | | IF | 0-0 | 22-21-21 | D00321A | DED | | | D41369J | DED | | | 115-199 |
| 5801 | 20 | | GA | | 1-6 | 31-41-12 | D41317J | | | DT | GD02207 | ST.. | 2 | | ALL |
| 5802 | 20 | | GA | | 1-6 | 31-41-12 | D41317J | | | DS | GD02207 | ST.. | 2 | | ALL |
| 5803 | 20 | | GA | | 1-6 | 31-41-19 | D41065J | | | DQ | GD02204 | ST.. | 2 | | ALL |
| 5804 | 20 | | GA | | 1-6 | 31-41-19 | D41065J | | | DR | GD02204 | ST.. | 2 | | ALL |
| 5805 | 20 | | GA | | 1-6 | 31-41-22 | D41369J | | | EK | GD02201 | ST.. | 2 | | ALL |
| 5806 | 20 | | GA | | 1-6 | 31-41-22 | D41369J | | | EL | GD02201 | ST.. | 2 | | ALL |
| 5810 | 20 | | GA | | 1-6 | 22-32-12 | D41317J | | | CK | GD02207 | ST.. | 2 | | ALL |
| 5811 | 20 | | GA | | 1-6 | 22-32-12 | D41369J | | | CL | GD02201 | ST.. | 2 | | ALL |
| 5813 | 20 | | GA | | 1-6 | 34-61-15 | D41317J | | | EV | GD02207 | ST.. | 2 | | ALL |
| 5814 | 20 | | GA | | 1-6 | 34-61-14 | D41317J | | | HS | GD02207 | ST.. | 2 | | ALL |
| 5815 | 20 | | GA | | 1-6 | 34-61-24 | D41369J | | | JA | GD02201 | ST.. | 2 | | ALL |
| 5816 | 20 | | GA | | 1-6 | 34-61-25 | D41369J | | | JB | GD02201 | ST.. | 2 | | ALL |
| 5818 | 24 | | GK | | 2-11 | 24-28-21 | D00321E | E12 | | | D41451J | 30 | | *H | ALL |
| 5819 | 24 | | GK | | 3-8 | 24-28-21 | D00319E | E12 | | | D41451J | 30 | | *H | 001-099 |
| 5819 | 24 | | GK | | 3-7 | 24-28-21 | D00319E | E12 | | | D41451J | 30 | | *H | 115-199 |
| 5821 | 24 | | GK | | 2-11 | 24-28-21 | D00321E | E09 | | | D41451J | 28 | | *H | ALL |
| 5822 | 24 | | GK | | 3-8 | 24-28-21 | D00319E | E09 | | | D41451J | 28 | | *H | 001-099 |
| 5822 | 24 | | GK | | 3-7 | 24-28-21 | D00319E | E09 | | | D41451J | 28 | | *H | 115-199 |
| 5824 | 24 | | GK | | 2-11 | 24-28-21 | D00321E | E10 | | | D41451J | 29 | | *H | ALL |
| 5825 | 24 | | GK | | 3-8 | 24-28-21 | D00319E | E10 | | | D41451J | 29 | | *H | 001-099 |
| 5825 | 24 | | GK | | 3-7 | 24-28-21 | D00319E | E10 | | | D41451J | 29 | | *H | 115-199 |
| 5827 | 24 | | GK | | 3-8 | 24-28-21 | D00319E | E11 | | | D41451J | 31 | | *H | 001-099 |
| 5827 | 24 | | GK | | 3-7 | 24-28-21 | D00319E | E11 | | | D41451J | 31 | | *H | 115-199 |
| 5828 | 24 | | GK | | 2-11 | 24-28-21 | D00321E | E11 | | | D41451J | 31 | | *H | ALL |
| 5836 | 24 | | GK | | 2-10 | 74-31-11 | D00321B | H15 | | | D41738J | 23 | | *R | 001-099 |
| 5836 | 24 | | GK | | 4-10 | 74-31-11 | D00321B | H15 | | | D41764J | 26 | | *S | 115-199 |
| 5837 | 24 | | GK | | 4-1 | 74-31-11 | D00319B | H15 | | | D41738J | 23 | | *R | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 133

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | From | | To | | | Effectivity | | | | | |
|------------------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|-------------|---------|-------|------|------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5837 | 24 | | GK | | 3-5 | 74-31-11 | D00319B | H15 | | | D41764J | 26 | | *S | 115-199 |
| 5839 | 24 | | GK | | 3-6 | 74-31-21 | D00321B | K02 | | | D41776J | 24 | | *V | 001-099 |
| 5839 | 24 | | GK | | 2-11 | 74-31-21 | D00321B | K02 | | | D41774J | 21 | | *U | 115-199 |
| 5840 | 24 | | GK | | 3-1 | 74-31-21 | D00319B | K02 | | | D41776J | 24 | | *V | 001-099 |
| 5840 | 24 | | GK | | 4-2 | 74-31-21 | D00319B | K02 | | | D41774J | 21 | | *U | 115-199 |
| 5842 | 24 | | GK | | 3-4 | 75-31-11 | D00321D | J03 | | | D41788J | 3 | | *1 | 115-199 |
| 5843 | 24 | | GK | | 4-5 | 75-31-11 | D00319D | J03 | | | D41788J | 3 | | *1 | 115-199 |
| 5845 | 24 | | GK | | 5-5 | 75-31-11 | D00321B | J10 | | | D41772J | 2 | | *T | 115-199 |
| 5846 | 24 | | GK | | 4-0 | 75-31-11 | D00319B | J10 | | | D41772J | 2 | | *T | 115-199 |
| 5848 | 24 | | GK | | 2-10 | 77-12-41 | D00321F | J10 | | | D41738J | 20 | | *R | 001-099 |
| 5848 | 24 | | GK | | 2-11 | 77-12-41 | D00321F | J10 | | | D41738J | 20 | | *R | 115-199 |
| 5849 | 24 | | GK | | 4-0 | 77-12-41 | D00319F | J10 | | | D41738J | 20 | | *R | ALL |
| 5851 | 24 | | GK | | 3-3 | 77-12-42 | D00321F | B10 | | | D41776J | 11 | | *V | ALL |
| 5852 | 24 | | GK | | 3-0 | 77-12-42 | D00319F | B10 | | | D41776J | 11 | | *V | 001-099 |
| 5852 | 24 | | GK | | 2-11 | 77-12-42 | D00319F | B10 | | | D41776J | 11 | | *V | 115-199 |
| 5855 | 24 | | GK | | 2-4 | 79-31-11 | TB0207Z | 77 | BJ | | TB0207Y | A095 | BJ | | 001-099 |
| 5856 | 24 | | GK | | 2-11 | 79-31-11 | D00321F | G10 | | | TB0207Z | 78 | BJ | | 001, 003-099 |
| 5856 | 24 | | GK | | 2-10 | 79-31-11 | D00321F | G10 | | | TB0207Z | 78 | BJ | | 002 |
| 5856 | 24 | | GK | | 3-0 | 79-31-11 | D00321F | G10 | | | TB0207Z | 78 | BJ | | 115-199 |
| 5857 | 24 | | GK | | 3-2 | 79-31-11 | D00319E | E04 | | | TB0207Y | A095 | BJ | | 001, 003-099 |
| 5857 | 24 | | GK | | 3-3 | 79-31-11 | D00319E | E04 | | | TB0207Y | A095 | BJ | | 002 |
| 5857 | 24 | | GK | | 2-11 | 79-31-11 | D00319E | E04 | | | TB0207Z | 77 | BJ | | 115-199 |
| 5858 | 24 | | GK | | 2-11 | 79-31-11 | D00321E | G13 | | | TB0207Y | A079 | BJ | | 001, 003-099 |
| 5858 | 24 | | GK | | 3-0 | 79-31-11 | D00321E | G13 | | | TB0207Y | A079 | BJ | | 002 |
| 5858 | 24 | | GK | | 3-1 | 79-31-11 | D00321E | G13 | | | TB0207Y | A079 | BJ | | 115-199 |
| 5859 | 24 | | GK | | 2-9 | 79-31-11 | D00319E | G13 | | | TB0207Y | A079 | BJ | | 001, 003-099 |
| 5859 | 24 | | GK | | 2-10 | 79-31-11 | D00319E | G13 | | | TB0207Y | A079 | BJ | | 002 |
| 5859 | 24 | | GK | | 2-11 | 79-31-11 | D00319E | G13 | | | TB0207Y | A079 | BJ | | 115-199 |
| 5860 | 24 | | GK | | 3-0 | 79-31-11 | D00321B | J08 | | | TB0207Y | C079 | BJ | | 001, 003-099 |
| 5860 | 24 | | GK | | 3-1 | 79-31-11 | D00321B | J08 | | | TB0207Y | C079 | BJ | | 002 |
| 5860 | 24 | | GK | | 3-2 | 79-31-11 | D00321B | J08 | | | TB0207Y | C079 | BJ | | 115-199 |
| 5861 | 24 | | GK | | 2-9 | 79-31-11 | D00319B | J08 | | | TB0207Y | C079 | BJ | | 001-099 |
| 5861 | 24 | | GK | | 2-11 | 79-31-11 | D00319B | J08 | | | TB0207Y | C079 | BJ | | 115-199 |
| 5862 | 24 | | GK | | 3-1 | 79-32-11 | D00321D | F15 | | | TB0207Y | C083 | BJ | | 001-099 |
| 5862 | 24 | | GK | | 4-9 | 79-32-11 | D00321D | F15 | | | TB0207Y | C001 | BJ | | 115-199 |
| 5863 | 24 | | GK | | 2-11 | 79-32-11 | D00319D | F15 | | | TB0207Y | C083 | BJ | | 001-099 |
| 5863 | 24 | | GK | | 3-6 | 79-32-11 | D00319D | F15 | | | TB0207Y | C001 | BJ | | 115-199 |
| 5864 | 24 | | GK | | 4-11 | 79-32-11 | D00321E | H11 | | | TB0207Y | A001 | BJ | | 001, 003-099 |
| 5864 | 24 | | GK | | 4-10 | 79-32-11 | D00321E | H11 | | | TB0207Y | A001 | BJ | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 134

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5864 | 24 | | GK | | 4-8 | 79-32-11 | D00321E | | H11 | | TB0207Y | A001 | BJ | | 115-199 |
| 5865 | 24 | | GK | | 3-6 | 79-32-11 | D00319E | | H11 | | TB0207Y | A001 | BJ | | 001, 003-099 |
| 5865 | 24 | | GK | | 3-5 | 79-32-11 | D00319E | | H11 | | TB0207Y | A001 | BJ | | 002 |
| 5865 | 24 | | GK | | 3-4 | 79-32-11 | D00319E | | H11 | | TB0207Y | A001 | BJ | | 115-199 |
| 5866 | 24 | | GK | | 3-1 | 79-32-11 | D00321B | | G01 | | TB0207Y | C084 | BJ | | 001-099 |
| 5866 | 24 | | GK | | 4-9 | 79-32-11 | D00321B | | G01 | | TB0207Y | C002 | BJ | | 115-199 |
| 5867 | 24 | | GK | | 2-9 | 79-32-11 | D00319B | | G01 | | TB0207Y | C084 | BJ | | 001-099 |
| 5867 | 24 | | GK | | 3-4 | 79-32-11 | D00319B | | G01 | | TB0207Y | C002 | BJ | | 115-199 |
| 5868 | 24 | | GK | | 5-0 | 79-32-11 | D00321B | | H02 | | TB0207Y | A002 | BJ | | 001, 003-099 |
| 5868 | 24 | | GK | | 4-11 | 79-32-11 | D00321B | | H02 | | TB0207Y | A002 | BJ | | 002 |
| 5868 | 24 | | GK | | 4-9 | 79-32-11 | D00321B | | H02 | | TB0207Y | A002 | BJ | | 115-199 |
| 5869 | 24 | | GK | | 3-7 | 79-32-11 | D00319B | | H02 | | TB0207Y | A002 | BJ | | 001, 003-099 |
| 5869 | 24 | | GK | | 3-6 | 79-32-11 | D00319B | | H02 | | TB0207Y | A002 | BJ | | 002 |
| 5869 | 24 | | GK | | 3-4 | 79-32-11 | D00319B | | H02 | | TB0207Y | A002 | BJ | | 115-199 |
| 5871 | 24 | | GK | | 2-9 | 80-11-21 | D00321F | | B05 | | D41774J | 18 | | *U | 001-099 |
| 5871 | 24 | | GK | | 2-11 | 80-11-21 | D00321F | | B05 | | D41774J | 18 | | *U | 115-199 |
| 5872 | 24 | | GK | | 3-6 | 80-11-21 | D00319F | | B05 | | D41774J | 18 | | *U | 001-099 |
| 5872 | 24 | | GK | | 4-0 | 80-11-21 | D00319F | | B05 | | D41774J | 18 | | *U | 115-199 |
| 5874 | 24 | | GK | | 2-1 | 31-41-14 | D42073J | | 14 | | TB0207Y | A065 | BJ | | 001, 003-099 |
| 5874 | 24 | | GK | | 2-2 | 31-41-14 | D42073J | | 14 | | TB0207Y | A065 | BJ | | 002 |
| 5874 | 24 | | GK | | 2-4 | 31-41-14 | D42073J | | 14 | | TB0207Y | A065 | BJ | | 115-199 |
| 5875 | 24 | | GK | | 2-8 | 31-41-14 | D00319A | | E10 | | D42185J | 8 | | | 001-099 |
| 5875 | 24 | | GK | | 2-9 | 31-41-14 | D00319A | | E10 | | D42185J | 8 | | | 115-199 |
| 5876 | 24 | | GK | | 2-6 | 31-41-14 | D00319A | | F08 | | TB0207Y | A065 | BJ | | 001, 003-099 |
| 5876 | 24 | | GK | | 2-7 | 31-41-14 | D00319A | | F08 | | TB0207Y | A065 | BJ | | 002 |
| 5876 | 24 | | GK | | 2-8 | 31-41-14 | D00319A | | F08 | | TB0207Y | A065 | BJ | | 115-199 |
| 5878 | 24 | | GK | | 3-8 | 31-41-14 | D00319A | | B03 | | D41069J | 28 | | *1 | 001-099 |
| 5878 | 24 | | GK | | 3-7 | 31-41-14 | D00319A | | B03 | | D41069J | 28 | | *1 | 115-199 |
| 5880 | 24 | | GK | | 3-8 | 31-41-14 | D00319A | | C03 | | D41069J | 29 | | *1 | 001-099 |
| 5880 | 24 | | GK | | 3-7 | 31-41-14 | D00319A | | C03 | | D41069J | 29 | | *1 | 115-199 |
| 5882 | 24 | | GK | | 3-8 | 31-41-14 | D00319A | | A03 | | D41069J | 30 | | *1 | 001-099 |
| 5882 | 24 | | GK | | 3-7 | 31-41-14 | D00319A | | A03 | | D41069J | 30 | | *1 | 115-199 |
| 5884 | 24 | | GK | | 2-8 | 31-41-14 | D00319A | | C04 | | D41071J | 28 | | *1 | 001-099 |
| 5884 | 24 | | GK | | 2-9 | 31-41-14 | D00319A | | C04 | | D41071J | 28 | | *1 | 115-199 |
| 5886 | 24 | | GK | | 2-8 | 31-41-14 | D00319A | | C05 | | D41071J | 29 | | *1 | 001-099 |
| 5886 | 24 | | GK | | 2-9 | 31-41-14 | D00319A | | C05 | | D41071J | 29 | | *1 | 115-199 |
| 5888 | 24 | | GK | | 2-8 | 31-41-14 | D00319A | | C06 | | D41071J | 30 | | *1 | 001-099 |
| 5888 | 24 | | GK | | 2-9 | 31-41-14 | D00319A | | C06 | | D41071J | 30 | | *1 | 115-199 |
| 5890 | 24 | | GK | | 2-7 | 31-41-14 | D00319B | | J15 | | D42073J | 2 | | *1 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 135

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5890 | 24 | | GK | | 2-8 | 31-41-14 | D00319B | J15 | | | D42073J | 2 | | *1 | 115-199 |
| 5891 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | F11 | | | D00755 | 6 | VJ | | 001-010 |
| 5891 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | F11 | | | D00755 | 6 | VJ | | 011-099 |
| 5891 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | F11 | | | D00755 | 6 | | | 115-199 |
| 5892 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | F07 | | | D00755 | 7 | VP | | 001-010, 115-199 |
| 5892 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | F07 | | | D00755 | 7 | VP | | 011-099 |
| 5893 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | F02 | | | D00755 | 8 | VJ | | 001-010 |
| 5893 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | F02 | | | D00755 | 8 | VJ | | 011-099 |
| 5893 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | F02 | | | D00755 | 8 | | | 115-199 |
| 5894 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | F10 | | | D00755 | 9 | VP | | 001-010, 115-199 |
| 5894 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | F10 | | | D00755 | 9 | VP | | 011-099 |
| 5895 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | F06 | | | D00755 | 10 | VP | | 001-010, 115-199 |
| 5895 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | F06 | | | D00755 | 10 | VP | | 011-099 |
| 5896 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | C09 | | | D00755 | 13 | VP | | 001-010, 115-199 |
| 5896 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | C09 | | | D00755 | 13 | VP | | 011-099 |
| 5897 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | C06 | | | D00755 | 14 | VP | | 001-010, 115-199 |
| 5897 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | C06 | | | D00755 | 14 | VP | | 011-099 |
| 5898 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | D03 | | | D00755 | 15 | VP | | 001-010, 115-199 |
| 5898 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | D03 | | | D00755 | 15 | VP | | 011-099 |
| 5899 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | D11 | | | D00755 | 16 | VP | | 001-010, 115-199 |
| 5899 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | D11 | | | D00755 | 16 | VP | | 011-099 |
| 5900 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | B06 | | | D00755 | 17 | VP | | 001-010, 115-199 |
| 5900 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | B06 | | | D00755 | 17 | VP | | 011-099 |
| 5901 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | E13 | | | D00755 | 18 | VP | | 001-010, 115-199 |
| 5901 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | E13 | | | D00755 | 18 | VP | | 011-099 |
| 5902 | 24 | | GK | | 2-7 | 31-41-14 | D00319D | E10 | | | D00755 | 1 | VJ | | 001-008 |
| 5902 | 24 | | GK | | 3-0 | 31-41-14 | D00319D | E10 | | | D00755 | 1 | VJ | | 009-099 |
| 5902 | 24 | | GK | | 2-8 | 31-41-14 | D00319D | E10 | | | D00755 | 1 | | | 115-199 |
| 5903 | 24 | | GK | | 2-7 | 31-41-14 | D00319D | E04 | | | D00755 | 2 | VP | | 001-010 |
| 5903 | 24 | | GK | | 2-9 | 31-41-14 | D00319D | E04 | | | D00755 | 2 | VP | | 011-099 |
| 5903 | 24 | | GK | | 2-8 | 31-41-14 | D00319D | E04 | | | D00755 | 2 | VP | | 115-199 |
| 5904 | 24 | | GK | | 2-7 | 31-41-14 | D00319D | E06 | | | D00755 | 3 | VJ | | 001-010 |
| 5904 | 24 | | GK | | 2-9 | 31-41-14 | D00319D | E06 | | | D00755 | 3 | VJ | | 011-099 |
| 5904 | 24 | | GK | | 2-8 | 31-41-14 | D00319D | E06 | | | D00755 | 3 | | | 115-199 |
| 5905 | 24 | | GK | | 2-7 | 31-41-14 | D00319D | E11 | | | D00755 | 4 | VP | | 001-010 |
| 5905 | 24 | | GK | | 2-9 | 31-41-14 | D00319D | E11 | | | D00755 | 4 | VP | | 011-099 |
| 5905 | 24 | | GK | | 2-8 | 31-41-14 | D00319D | E11 | | | D00755 | 4 | VP | | 115-199 |
| 5906 | 24 | | GK | | 2-7 | 31-41-14 | D00319D | E03 | | | D00755 | 5 | VJ | | 001-010 |
| 5906 | 24 | | GK | | 2-9 | 31-41-14 | D00319D | E03 | | | D00755 | 5 | VJ | | 011-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 136

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5906 | 24 | | GK | | 2-8 | 31-41-14 | D00319D | E03 | | | D00755 | 5 | | | 115-199 |
| 5907 | 24 | | GK | | 2-7 | 31-41-14 | D00319D | D08 | | | D00755 | 20 | VP | | 001-010 |
| 5907 | 24 | | GK | | 2-9 | 31-41-14 | D00319D | D08 | | | D00755 | 20 | VP | | 011-099 |
| 5907 | 24 | | GK | | 2-8 | 31-41-14 | D00319D | D08 | | | D00755 | 20 | VP | | 115-199 |
| 5908 | 24 | | GK | | 2-4 | 31-41-14 | D00319F | B07 | | | D00755 | 11 | VP | | 001-010 |
| 5908 | 24 | | GK | | 2-6 | 31-41-14 | D00319F | B07 | | | D00755 | 11 | VP | | 011-099 |
| 5908 | 24 | | GK | | 2-5 | 31-41-14 | D00319F | B07 | | | D00755 | 11 | VP | | 115-199 |
| 5909 | 24 | | GK | | 2-4 | 31-41-14 | D00319F | D08 | | | D00755 | 12 | VP | | 001-010 |
| 5909 | 24 | | GK | | 2-6 | 31-41-14 | D00319F | D08 | | | D00755 | 12 | VP | | 011-099 |
| 5909 | 24 | | GK | | 2-5 | 31-41-14 | D00319F | D08 | | | D00755 | 12 | VP | | 115-199 |
| 5910 | 24 | | GK | | 2-5 | 31-41-14 | D00319E | G01 | | | D00755 | 19 | VP | | 001-010 |
| 5910 | 24 | | GK | | 2-8 | 31-41-14 | D00319E | G01 | | | D00755 | 19 | VP | | 011-099 |
| 5910 | 24 | | GK | | 2-6 | 31-41-14 | D00319E | G01 | | | D00755 | 19 | VP | | 115-199 |
| 5911 | 22 | | GA | | 2-3 | 31-41-14 | D00755 | 33 | VJ | | GD02218 | ST.. | 2 | | 001-010 |
| 5911 | 22 | | GA | | 2-6 | 31-41-14 | D00755 | 33 | VJ | | GD02218 | ST.. | 2 | | 011-099 |
| 5911 | 22 | | GA | | 2-4 | 31-41-14 | D00755 | 33 | | | GD02218 | ST.. | 2 | | 115-199 |
| 5912 | 22 | | GA | | 0-6 | 31-41-14 | D00319A | K15 | | | GD02218 | ST.. | 2 | | ALL |
| 5913 | 22 | | GA | | 0-6 | 31-41-14 | D00319B | K15 | | | GD02218 | ST.. | 2 | | ALL |
| 5914 | 22 | | GA | | 0-6 | 31-41-14 | D00319E | K15 | | | GD02218 | ST.. | 2 | | ALL |
| 5915 | 22 | | GA | | 0-6 | 31-41-14 | D00319D | K15 | | | GD02218 | ST.. | 2 | | ALL |
| 5916 | 24 | | GK | | 5-4 | 31-41-24 | D00321A | E10 | | | D41867J | 29 | | | 001-099 |
| 5916 | 24 | | G1 | JJ | 5-5 | 31-41-24 | D00321A | E10 | | | D41867J | 29 | | | 115-199 |
| 5916Z | | | | JJ | 0-0 | 31-41-24 | D00321A | DED | | | D41867J | DED | | | 115-199 |
| 5917 | 24 | | GK | | 3-6 | 31-41-24 | D00321A | F08 | | | TB0207Y | A065 | BJ | | 001, 003-099 |
| 5917 | 24 | | GK | | 3-7 | 31-41-24 | D00321A | F08 | | | TB0207Y | A065 | BJ | | 002 |
| 5917 | 24 | | GK | | 3-8 | 31-41-24 | D00321A | F08 | | | TB0207Y | A065 | BJ | | 115-199 |
| 5918 | 24 | | GK | | 5-1 | 31-41-24 | D00321A | B03 | | | D41069J | 28 | | *1 | 001-099 |
| 5918 | 24 | | GK | | 4-11 | 31-41-24 | D00321A | B03 | | | D41069J | 28 | | *1 | 115-199 |
| 5919 | 24 | | GK | | 5-1 | 31-41-24 | D00321A | C03 | | | D41069J | 29 | | *1 | 001-099 |
| 5919 | 24 | | GK | | 4-11 | 31-41-24 | D00321A | C03 | | | D41069J | 29 | | *1 | 115-199 |
| 5920 | 24 | | GK | | 5-1 | 31-41-24 | D00321A | A03 | | | D41069J | 30 | | *1 | 001-099 |
| 5920 | 24 | | GK | | 4-11 | 31-41-24 | D00321A | A03 | | | D41069J | 30 | | *1 | 115-199 |
| 5921 | 24 | | GK | | 4-1 | 31-41-24 | D00321A | C04 | | | D41071J | 28 | | *1 | ALL |
| 5922 | 24 | | GK | | 4-1 | 31-41-24 | D00321A | C05 | | | D41071J | 29 | | *1 | ALL |
| 5923 | 24 | | GK | | 4-1 | 31-41-24 | D00321A | C06 | | | D41071J | 30 | | *1 | ALL |
| 5924 | 24 | | GK | | 3-7 | 31-41-24 | D00321B | J15 | | | D42073J | 2 | | *1 | 001-099 |
| 5924 | 24 | | GK | | 3-8 | 31-41-24 | D00321B | J15 | | | D42073J | 2 | | *1 | 115-199 |
| 5925 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | F11 | | | D00757 | 6 | VJ | | 001-010 |
| 5925 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | F11 | | | D00757 | 6 | VJ | | 011-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 137

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5925 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | F11 | | | D00757 | 6 | VJ | | 115-199 |
| 5926 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | F07 | | | D00757 | 7 | VP | | 001-010 |
| 5926 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | F07 | | | D00757 | 7 | VP | | 011-099 |
| 5926 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | F07 | | | D00757 | 7 | VP | | 115-199 |
| 5927 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | F02 | | | D00757 | 8 | VJ | | 001-010 |
| 5927 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | F02 | | | D00757 | 8 | VJ | | 011-099 |
| 5927 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | F02 | | | D00757 | 8 | VJ | | 115-199 |
| 5928 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | F10 | | | D00757 | 9 | VP | | 001-010 |
| 5928 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | F10 | | | D00757 | 9 | VP | | 011-099 |
| 5928 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | F10 | | | D00757 | 9 | VP | | 115-199 |
| 5929 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | F06 | | | D00757 | 10 | VP | | 001-010 |
| 5929 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | F06 | | | D00757 | 10 | VP | | 011-099 |
| 5929 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | F06 | | | D00757 | 10 | VP | | 115-199 |
| 5930 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | C09 | | | D00757 | 13 | VP | | 001-010 |
| 5930 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | C09 | | | D00757 | 13 | VP | | 011-099 |
| 5930 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | C09 | | | D00757 | 13 | VP | | 115-199 |
| 5931 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | C06 | | | D00757 | 14 | VP | | 001-010 |
| 5931 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | C06 | | | D00757 | 14 | VP | | 011-099 |
| 5931 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | C06 | | | D00757 | 14 | VP | | 115-199 |
| 5932 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | D03 | | | D00757 | 15 | VP | | 001-010 |
| 5932 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | D03 | | | D00757 | 15 | VP | | 011-099 |
| 5932 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | D03 | | | D00757 | 15 | VP | | 115-199 |
| 5933 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | D11 | | | D00757 | 16 | VP | | 001-010 |
| 5933 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | D11 | | | D00757 | 16 | VP | | 011-099 |
| 5933 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | D11 | | | D00757 | 16 | VP | | 115-199 |
| 5934 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | B06 | | | D00757 | 17 | VP | | 001-010 |
| 5934 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | B06 | | | D00757 | 17 | VP | | 011-099 |
| 5934 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | B06 | | | D00757 | 17 | VP | | 115-199 |
| 5935 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | E13 | | | D00757 | 18 | VP | | 001-010 |
| 5935 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | E13 | | | D00757 | 18 | VP | | 011-099 |
| 5935 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | E13 | | | D00757 | 18 | VP | | 115-199 |
| 5936 | 24 | | GK | | 2-7 | 31-41-24 | D00321D | E10 | | | D00757 | 1 | VJ | | 001-008 |
| 5936 | 24 | | GK | | 3-0 | 31-41-24 | D00321D | E10 | | | D00757 | 1 | VJ | | 009-099 |
| 5936 | 24 | | GK | | 2-8 | 31-41-24 | D00321D | E10 | | | D00757 | 1 | VJ | | 115-199 |
| 5937 | 24 | | GK | | 2-7 | 31-41-24 | D00321D | E04 | | | D00757 | 2 | VP | | 001-010 |
| 5937 | 24 | | GK | | 2-10 | 31-41-24 | D00321D | E04 | | | D00757 | 2 | VP | | 011-099 |
| 5937 | 24 | | GK | | 2-8 | 31-41-24 | D00321D | E04 | | | D00757 | 2 | VP | | 115-199 |
| 5938 | 24 | | GK | | 2-7 | 31-41-24 | D00321D | E06 | | | D00757 | 3 | VJ | | 001-010 |
| 5938 | 24 | | GK | | 2-10 | 31-41-24 | D00321D | E06 | | | D00757 | 3 | VJ | | 011-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 138

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5938 | 24 | | GK | | 2-8 | 31-41-24 | D00321D | E06 | | | D00757 | 3 | VJ | | 115-199 |
| 5939 | 24 | | GK | | 2-7 | 31-41-24 | D00321D | E11 | | | D00757 | 4 | VP | | 001-010 |
| 5939 | 24 | | GK | | 2-10 | 31-41-24 | D00321D | E11 | | | D00757 | 4 | VP | | 011-099 |
| 5939 | 24 | | GK | | 2-8 | 31-41-24 | D00321D | E11 | | | D00757 | 4 | VP | | 115-199 |
| 5940 | 24 | | GK | | 2-7 | 31-41-24 | D00321D | E03 | | | D00757 | 5 | VP | | 001-010 |
| 5940 | 24 | | GK | | 2-10 | 31-41-24 | D00321D | E03 | | | D00757 | 5 | VP | | 011-099 |
| 5940 | 24 | | GK | | 2-8 | 31-41-24 | D00321D | E03 | | | D00757 | 5 | VP | | 115-199 |
| 5941 | 24 | | GK | | 2-7 | 31-41-24 | D00321D | D08 | | | D00757 | 20 | VP | | 001-010 |
| 5941 | 24 | | GK | | 2-10 | 31-41-24 | D00321D | D08 | | | D00757 | 20 | VP | | 011-099 |
| 5941 | 24 | | GK | | 2-8 | 31-41-24 | D00321D | D08 | | | D00757 | 20 | VP | | 115-199 |
| 5942 | 24 | | GK | | 2-4 | 31-41-24 | D00321F | B07 | | | D00757 | 11 | VP | | 001-010 |
| 5942 | 24 | | GK | | 2-7 | 31-41-24 | D00321F | B07 | | | D00757 | 11 | VP | | 011-099 |
| 5942 | 24 | | GK | | 2-5 | 31-41-24 | D00321F | B07 | | | D00757 | 11 | VP | | 115-199 |
| 5943 | 24 | | GK | | 2-4 | 31-41-24 | D00321F | D08 | | | D00757 | 12 | VP | | 001-010 |
| 5943 | 24 | | GK | | 2-7 | 31-41-24 | D00321F | D08 | | | D00757 | 12 | VP | | 011-099 |
| 5943 | 24 | | GK | | 2-5 | 31-41-24 | D00321F | D08 | | | D00757 | 12 | VP | | 115-199 |
| 5944 | 24 | | GK | | 2-6 | 31-41-24 | D00321E | G01 | | | D00757 | 19 | VP | | 001-010 |
| 5944 | 24 | | GK | | 2-9 | 31-41-24 | D00321E | G01 | | | D00757 | 19 | VP | | 011-099 |
| 5944 | 24 | | GK | | 2-7 | 31-41-24 | D00321E | G01 | | | D00757 | 19 | VP | | 115-199 |
| 5945 | 22 | | GA | | 2-3 | 31-41-24 | D00757 | 33 | VJ | | GD02220 | ST.. | 2 | | 001-010 |
| 5945 | 22 | | GA | | 2-6 | 31-41-24 | D00757 | 33 | VJ | | GD02220 | ST.. | 2 | | 011-099 |
| 5945 | 22 | | GA | | 2-4 | 31-41-24 | D00757 | 33 | VJ | | GD02220 | ST.. | 2 | | 115-199 |
| 5946 | 22 | | GA | | 2-8 | 31-41-24 | D00321A | K15 | | | GD02220 | ST.. | 2 | | ALL |
| 5947 | 22 | | GA | | 0-6 | 31-41-24 | D00321B | K15 | | | GD02220 | ST.. | 2 | | ALL |
| 5948 | 22 | | GA | | 0-6 | 31-41-24 | D00321D | K15 | | | GD02220 | ST.. | 2 | | ALL |
| 5949 | 22 | | GA | | 0-6 | 31-41-24 | D00321E | K15 | | | GD02220 | ST.. | 2 | | ALL |
| 5952 | 22 | | GA | | 2-6 | 31-41-21 | D40704J | 4 | | | TB0207Y | A052 | BJ | | 001-099 |
| 5952 | 22 | | GT | JF | 2-7 | 31-41-21 | D40704J | 4 | | | TB0207Y | A052 | BJ | | 115-199 |
| 5952Z | | | | JF | 0-0 | 31-41-21 | D40704J | DED | | | TB0207Y | DED | | | 115-199 |
| 5953 | 22 | | GA | | 1-0 | 79-34-11 | D41736J | | | AA | GD02211 | ST.. | 2 | | 001-099 |
| 5953 | 20 | | GA | | 1-6 | 79-34-11 | D41736J | | | AA | GD02211 | ST.. | 2 | | 115-199 |
| 5954 | 22 | | GA | | 1-0 | 79-34-11 | D41734J | | | AG | GD02211 | ST.. | 2 | | 001-099 |
| 5954 | 20 | | GA | | 1-6 | 79-34-11 | D41734J | | | AG | GD02211 | ST.. | 2 | | 115-199 |
| 5955 | 24 | | GK | | 3-4 | 27-09-14 | D41867J | 42 | | | TB0207Y | A041 | BJ | | 001, 003-099 |
| 5955 | 24 | | GK | | 3-5 | 27-09-14 | D41867J | 42 | | | TB0207Y | A041 | BJ | | 002, 115-199 |
| 5957 | 24 | | GK | | 3-4 | 27-09-14 | D41867J | 46 | | | TB0207Y | C041 | BJ | | 001, 003-099 |
| 5957 | 24 | | GK | | 3-5 | 27-09-14 | D41867J | 46 | | | TB0207Y | C041 | BJ | | 002, 115-199 |
| 5958 | 24 | | GK | | 2-7 | 27-09-14 | D42185J | 26 | | | TB0207Y | A041 | BJ | | 001, 003-099 |
| 5958 | 24 | | GK | | 2-8 | 27-09-14 | D42185J | 26 | | | TB0207Y | A041 | BJ | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 139

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5958 | 24 | | GK | | 2-9 | 27-09-14 | D42185J | | 26 | | TB0207Y | A041 | BJ | | 115-199 |
| 5959 | 24 | | GK | | 2-7 | 27-09-14 | D42185J | | 10 | | TB0207Y | C041 | BJ | | 001, 003-099 |
| 5959 | 24 | | GK | | 2-8 | 27-09-14 | D42185J | | 10 | | TB0207Y | C041 | BJ | | 002 |
| 5959 | 24 | | GK | | 2-9 | 27-09-14 | D42185J | | 32 | | TB0207Y | C041 | BJ | | 115-199 |
| 5963 | 24 | | GK | | 2-4 | 31-41-34 | D00319F | | B04 | | D00755 | 34 | VP | | 001-010 |
| 5963 | 24 | | GK | | 2-6 | 31-41-34 | D00319F | | B04 | | D00755 | 34 | VP | | 011-099 |
| 5963 | 24 | | GK | | 2-5 | 31-41-34 | D00319F | | B04 | | D00755 | 34 | VP | | 115-199 |
| 5964 | 24 | | GK | | 2-7 | 31-41-34 | D00319A | | J13 | | D00755 | 35 | VP | | 001-010 |
| 5964 | 24 | | GK | | 2-10 | 31-41-34 | D00319A | | J13 | | D00755 | 35 | VP | | 011-099 |
| 5964 | 24 | | GK | | 2-8 | 31-41-34 | D00319A | | J13 | | D00755 | 35 | VP | | 115-199 |
| 5965 | 24 | | GK | | 2-4 | 31-41-34 | D00321F | | B04 | | D00757 | 34 | VP | | 001-010 |
| 5965 | 24 | | GK | | 2-7 | 31-41-34 | D00321F | | B04 | | D00757 | 34 | VP | | 011-099 |
| 5965 | 24 | | GK | | 2-5 | 31-41-34 | D00321F | | B04 | | D00757 | 34 | VP | | 115-199 |
| 5966 | 24 | | GK | | 2-8 | 31-41-34 | D00321A | | J13 | | D00757 | 35 | VP | | 001-010 |
| 5966 | 24 | | GK | | 2-11 | 31-41-34 | D00321A | | J13 | | D00757 | 35 | VP | | 011-099 |
| 5966 | 24 | | GK | | 2-9 | 31-41-34 | D00321A | | J13 | | D00757 | 35 | VP | | 115-199 |
| 5970 | 22 | | GA | | 2-3 | 34-25-11 | D41879J | | | JC | GD02207 | ST.. | 2 | | 115-199 |
| 5971 | 22 | | GA | | 2-7 | 34-25-11 | D41867J | | | JD | GD02201 | ST.. | 2 | | 115-199 |
| 5973 | 24 | | GK | | 2-7 | 22-14-31 | D00319B | | J02 | | D41879J | 23 | | *Z | ALL |
| 5974 | 24 | | GK | | 4-0 | 22-14-31 | D00321B | | J02 | | D41879J | 23 | | *Z | ALL |
| 5976 | 24 | | GK | | 3-7 | 52-71-21 | D00319B | | C07 | | D41451J | 55 | | *H | 115-199 |
| 5977 | 24 | | GK | | 3-0 | 52-71-21 | D00321B | | C07 | | D41451J | 55 | | *H | 115-199 |
| 5978 | 24 | | GK | | 2-11 | 30-21-11 | D00319B | | H12 | | TB0207Y | A030 | BJ | | 001, 003-099 |
| 5978 | 24 | | GK | | 3-1 | 30-21-11 | D00319B | | H12 | | TB0207Y | A030 | BJ | | 002 |
| 5978 | 24 | | GK | | 3-0 | 30-21-11 | D00319B | | H12 | | TB0207Y | A030 | BJ | | 115-199 |
| 5979 | 24 | | GK | | 3-0 | 30-21-11 | D00319D | | J13 | | TB0207Y | C030 | BJ | | 001, 003-099 |
| 5979 | 24 | | GK | | 3-1 | 30-21-11 | D00319D | | J13 | | TB0207Y | C030 | BJ | | 002, 115-199 |
| 5980 | 24 | | GK | | 2-6 | 30-21-11 | D41734J | | 21 | | TB0207Y | C060 | BJ | | 001-099 |
| 5980 | 24 | | GK | | 2-7 | 30-21-11 | D41734J | | 21 | | TB0207Y | C060 | BJ | | 115-199 |
| 5981 | 24 | | GK | | 3-4 | 30-21-11 | D41734J | | 23 | | TB0207Y | A030 | BJ | | 001, 003-099, 115-199 |
| 5981 | 24 | | GK | | 3-5 | 30-21-11 | D41734J | | 23 | | TB0207Y | A030 | BJ | | 002 |
| 5982 | 24 | | GK | | 3-4 | 30-21-11 | D41734J | | 6 | | TB0207Y | A030 | BJ | | 001, 003-099, 115-199 |
| 5982 | 24 | | GK | | 3-5 | 30-21-11 | D41734J | | 6 | | TB0207Y | A030 | BJ | | 002 |
| 5983 | 24 | | GK | | 4-5 | 30-21-11 | D00321D | | J13 | | TB0207Y | C030 | BJ | | 001, 003-099, 115-199 |
| 5983 | 24 | | GK | | 4-6 | 30-21-11 | D00321D | | J13 | | TB0207Y | C030 | BJ | | 002 |
| 5984 | 24 | | GK | | 4-4 | 30-21-11 | D00321B | | H12 | | TB0207Y | A030 | BJ | | 001, 003-099 |
| 5984 | 24 | | GK | | 4-5 | 30-21-11 | D00321B | | H12 | | TB0207Y | A030 | BJ | | 002, 115-199 |
| 5985 | 24 | | GK | | 3-2 | 30-21-11 | D41736J | | 32 | | TB0207Y | A048 | BJ | | ALL |
| 5986 | 24 | | GK | | 3-7 | 30-21-11 | D41736J | | 33 | | TB0207Y | C030 | BJ | | 001, 003-099, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 140

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 5986 | 24 | | GK | | 3-8 | 30-21-11 | D41736J | 33 | | | TB0207Y | C030 | BJ | | 002 |
| 5987 | 24 | | GK | | 3-7 | 30-21-11 | D41736J | 7 | | | TB0207Y | C030 | BJ | | 001, 003-099, 115-199 |
| 5987 | 24 | | GK | | 3-8 | 30-21-11 | D41736J | 7 | | | TB0207Y | C030 | BJ | | 002 |
| 5989 | 22 | | GA | | 1-6 | 31-31-41 | D41451J | | | CA | GD02213 | ST.. | 2 | | 001-099 |
| 5989 | 22 | | GA | | 2-6 | 31-31-21 | D41451J | | | CA | GD02213 | ST.. | 2 | | 115-199 |
| 5990 | 24 | | GK | | 4-9 | 28-22-31 | D00321F | H04 | | | D41844J | 11 | | *X | 001-008 |
| 5990 | 24 | | GK | | 4-11 | 28-22-31 | D00321E | C02 | | | D41844J | 11 | | *X | 009-099 |
| 5990 | 24 | | GK | | 4-6 | 28-22-31 | D00321F | H04 | | | D41844J | 11 | | *X | 115-199 |
| 5991 | 24 | | GK | | 3-4 | 28-22-31 | D00319F | H04 | | | D41844J | 11 | | *X | 001-008 |
| 5991 | 24 | | GK | | 3-6 | 28-22-31 | D00319E | C02 | | | D41844J | 11 | | *X | 009-099 |
| 5991 | 24 | | GK | | 3-2 | 28-22-31 | D00319F | H04 | | | D41844J | 11 | | *X | 115-199 |
| 5993 | 24 | | GK | | 3-3 | 26-17-11 | D00321D | C10 | | | D41734J | 27 | | *P | ALL |
| 5994 | 24 | | GK | | 3-0 | 26-17-11 | D00319D | C10 | | | D41734J | 27 | | *P | 001-099 |
| 5994 | 24 | | GK | | 2-11 | 26-17-11 | D00319D | C10 | | | D41734J | 27 | | *P | 115-199 |
| 5995 | 20 | | GA | | 2-10 | 23-31-11 | D41058J | 29 | | | D42185J | 15 | | | 001-099 |
| 5995 | 20 | | GT | IT | 2-11 | 23-31-11 | D41058J | 29 | | | D42185J | 15 | | | 115-199 |
| 5995Z | | | | IT | 0-0 | 23-31-11 | D41058J | DED | | | D42185J | DED | | | 115-199 |
| 6002 | 24 | | GK | | 4-3 | 31-51-33 | D00321B | J11 | | | D41317J | 23 | | *F | 001-099 |
| 6002 | 24 | | GK | | 2-4 | 31-51-33 | D00321B | J11 | | | TB0207Z | 108 | BJ | | 115-199 |
| 6003 | 24 | | GK | | 2-10 | 31-51-33 | D00319B | J11 | | | D41317J | 23 | | *F | 001-099 |
| 6003 | 24 | | GK | | 3-7 | 31-51-33 | D00319B | J11 | | | TB0207Z | 108 | BJ | | 115-199 |
| 6006 | 24 | | GK | | 5-1 | 31-51-33 | D00321D | K06 | | | D41369J | 22 | | *G | 001-099 |
| 6006 | 24 | | GK | | 3-3 | 31-51-33 | D00321D | K06 | | | TB0207Z | 73 | BJ | | 115-199 |
| 6007 | 24 | | GK | | 3-9 | 31-51-33 | D00319D | K06 | | | D41369J | 22 | | *G | 001-099 |
| 6007 | 24 | | GK | | 3-0 | 31-51-33 | D00319D | K06 | | | TB0207Z | 73 | BJ | | 115-199 |
| 6009 | 24 | | GK | | 3-11 | 49-61-14 | D00321F | E01 | | | D41660J | 21 | | *K | ALL |
| 6010 | 24 | | GK | | 2-6 | 49-61-14 | D00319F | E01 | | | D41660J | 21 | | *K | 001-099 |
| 6010 | 24 | | GK | | 2-7 | 49-61-14 | D00319F | E01 | | | D41660J | 21 | | *K | 115-199 |
| 6012 | 24 | | GK | | 3-7 | 49-71-11 | D00319F | A05 | | | TB0207C | A122 | 2 | *1 | 001-099 |
| 6012 | 24 | | GK | | 3-5 | 49-71-11 | D00319F | A05 | | | TB0207C | A122 | 2 | *1 | 115-199 |
| 6013 | 24 | | GK | | 2-5 | 49-71-11 | D00321F | A05 | | | TB0207C | A122 | 2 | *1 | 001-099 |
| 6013 | 24 | | GK | | 2-4 | 49-71-11 | D00321F | A05 | | | TB0207C | A122 | 2 | *1 | 115-199 |
| 6014 | 24 | | GK | | 3-7 | 49-73-11 | D00319F | A06 | | | TB0207C | A121 | 2 | *1 | 001-099 |
| 6014 | 24 | | GK | | 3-5 | 49-73-11 | D00319F | A06 | | | TB0207C | A121 | 2 | *1 | 115-199 |
| 6015 | 24 | | GK | | 2-5 | 49-73-11 | D00321F | A06 | | | TB0207C | A121 | 2 | *1 | 001-099 |
| 6015 | 24 | | GK | | 2-4 | 49-73-11 | D00321F | A06 | | | TB0207C | A121 | 2 | *1 | 115-199 |
| 6016 | 24 | | GK | | 3-11 | 49-61-11 | D00321F | A10 | | | D41660J | 2 | | *K | ALL |
| 6017 | 24 | | GK | | 2-6 | 49-61-11 | D00319F | A10 | | | D41660J | 2 | | *K | 001-099 |
| 6017 | 24 | | GK | | 2-7 | 49-61-11 | D00319F | A10 | | | D41660J | 2 | | *K | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 141

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6019 | 22 | | GA | | 4-4 | 49-61-11 | D41660J | | 30 | | D41738J | 19 | | | 001-099 |
| 6019 | 22 | | GA | | 4-5 | 49-61-11 | D41660J | | 32 | | D41738J | 19 | | | 115-199 |
| 6020 | 22 | | GA | | 2-3 | 49-61-11 | D41660J | | 31 | | TB0207Y | A044 | BJ | | 001, 003-099, 115-199 |
| 6020 | 22 | | GA | | 2-4 | 49-61-11 | D41660J | | 31 | | TB0207Y | A044 | BJ | | 002 |
| 6021 | 22 | | GA | | 4-1 | 49-61-11 | D41738J | | 17 | | TB0207Y | A044 | BJ | | 001, 003-099 |
| 6021 | 22 | | GA | | 4-2 | 49-61-11 | D41738J | | 17 | | TB0207Y | A044 | BJ | | 002 |
| 6021 | 22 | | GA | | 4-3 | 49-61-11 | D41738J | | 17 | | TB0207Y | A044 | BJ | | 115-199 |
| 6023 | 24 | | GK | | 4-1 | 26-11-12 | D00319B | | E05 | | D41738J | 16 | | *R | 001-099 |
| 6023 | 24 | | GK | | 2-10 | 26-11-12 | D00319B | | E05 | | D41734J | 18 | | *P | 115-199 |
| 6024 | 24 | | GK | | 2-10 | 26-11-12 | D00321B | | E05 | | D41738J | 16 | | *R | 001-099 |
| 6024 | 24 | | GK | | 3-3 | 26-11-12 | D00321B | | E05 | | D41734J | 18 | | *P | 115-199 |
| 6026 | 22 | | GA | | 3-0 | 29-11-12 | D41628J | | 38 | | TB0207Y | A027 | BJ | | 001-099 |
| 6026 | 22 | | GA | | 4-8 | 29-11-12 | D41738J | | 21 | | TB0207Z | 27 | BJ | | 115-199 |
| 6027 | 22 | | GA | | 3-0 | 29-11-12 | D41628J | | 39 | | TB0207Y | C025 | BJ | | 001-099 |
| 6027 | 22 | | GA | | 2-6 | 29-11-12 | D41738J | | 23 | | TB0207Z | 103 | BJ | | 115-199 |
| 6028 | 22 | | GA | | 2-8 | 29-11-31 | D40214J | | 1 | | TB0207Z | 105 | BJ | | 001-099 |
| 6028 | 22 | | GA | | 2-7 | 29-11-31 | D40214J | | 1 | | TB0207Z | 105 | BJ | | 115-199 |
| 6029 | 22 | | GA | | 4-9 | 29-11-31 | D41844J | | 13 | | TB0207Z | 105 | BJ | | 001-099 |
| 6029 | 22 | | GA | | 4-5 | 29-11-31 | D41844J | | 13 | | TB0207Z | 105 | BJ | | 115-199 |
| 6030 | 24 | | GK | | 2-8 | 29-11-31 | D00321D | | J10 | | TB0207Z | 105 | BJ | | 001-099 |
| 6030 | 24 | | GK | | 2-7 | 29-11-31 | D00321D | | J10 | | TB0207Z | 105 | BJ | | 115-199 |
| 6031 | 24 | | GK | | 3-10 | 29-11-31 | D00319D | | J10 | | TB0207Z | 105 | BJ | | 001-099 |
| 6031 | 24 | | GK | | 3-8 | 29-11-31 | D00319D | | J10 | | TB0207Z | 105 | BJ | | 115-199 |
| 6032 | 22 | | GA | | 3-6 | 29-11-31 | D40214J | | 2 | | TB0207Y | C040 | BJ | | 001, 003-099 |
| 6032 | 22 | | GA | | 3-7 | 29-11-31 | D40214J | | 2 | | TB0207Y | C040 | BJ | | 002, 115-199 |
| 6033 | 22 | | GA | | 3-1 | 29-11-31 | D41844J | | 12 | | TB0207Y | C040 | BJ | | 001, 003-099 |
| 6033 | 22 | | GA | | 3-2 | 29-11-31 | D41844J | | 12 | | TB0207Y | C040 | BJ | | 002 |
| 6033 | 22 | | GA | | 2-10 | 29-11-31 | D41844J | | 12 | | TB0207Y | C040 | BJ | | 115-199 |
| 6034 | 24 | | GK | | 3-11 | 29-11-31 | D00321D | | J11 | | TB0207Y | C040 | BJ | | 001, 003-099 |
| 6034 | 24 | | GK | | 4-0 | 29-11-31 | D00321D | | J11 | | TB0207Y | C040 | BJ | | 002, 115-199 |
| 6035 | 24 | | GK | | 2-7 | 29-11-31 | D00319D | | J11 | | TB0207Y | C040 | BJ | | 001-099 |
| 6035 | 24 | | GK | | 2-8 | 29-11-31 | D00319D | | J11 | | TB0207Y | C040 | BJ | | 115-199 |
| 6036 | 22 | | GA | | 3-6 | 29-11-31 | D40214J | | 3 | | TB0207Y | A039 | BJ | | 001, 003-099 |
| 6036 | 22 | | GA | | 3-7 | 29-11-31 | D40214J | | 3 | | TB0207Y | A039 | BJ | | 002, 115-199 |
| 6037 | 22 | | GA | | 3-11 | 29-11-31 | D40584J | | 18 | | TB0207Y | A039 | BJ | | 001-099 |
| 6037 | 22 | | GA | | 4-0 | 29-11-31 | D40584J | | 18 | | TB0207Y | A039 | BJ | | 115-199 |
| 6038 | 24 | | GK | | 4-0 | 29-11-31 | D00321A | | G11 | | TB0207Y | A039 | BJ | | 001, 003-099 |
| 6038 | 24 | | GK | | 4-1 | 29-11-31 | D00321A | | G11 | | TB0207Y | A039 | BJ | | 002, 115-199 |
| 6039 | 24 | | GK | | 2-7 | 29-11-31 | D00319A | | G11 | | TB0207Y | A039 | BJ | | 001, 003-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 142

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6039 | 24 | | GK | | 2-8 | 29-11-31 | D00319A | G11 | | | TB0207Y | A039 | BJ | | 002, 115-199 |
| 6042 | 24 | | GK | | 3-0 | 29-22-11 | D00319D | K05 | | | D41734J | 1 | | *P | 001-099 |
| 6042 | 24 | | GK | | 2-11 | 29-22-11 | D00319D | K05 | | | D41734J | 20 | | *P | 115-199 |
| 6043 | 24 | | GK | | 3-3 | 29-22-11 | D00321D | K05 | | | D41734J | 1 | | *P | 001-099 |
| 6043 | 24 | | GK | | 3-3 | 29-22-11 | D00321D | K05 | | | D41734J | 20 | | *P | 115-199 |
| 6044 | 22 | | GA | | 4-0 | 29-11-12 | D41792J | 9 | | | D41628J | 15 | | | 001-099 |
| 6044 | 22 | | GA | | 4-8 | 29-11-12 | D41792J | 9 | | | D41632J | 10 | | | 115-199 |
| 6045 | 22 | | GA | | 2-7 | 29-11-22 | D41794J | 9 | | | TB0207Z | 13 | BJ | | 001, 003-099, 115-199 |
| 6045 | 22 | | GA | | 2-8 | 29-11-22 | D41794J | 9 | | | TB0207Z | 13 | BJ | | 002 |
| 6046 | 22 | | GA | | 3-0 | 29-11-22 | D41794J | 5 | | | TB0207Y | A024 | BJ | | 001, 003-099 |
| 6046 | 22 | | GA | | 3-1 | 29-11-22 | D41794J | 5 | | | TB0207Y | A024 | BJ | | 002 |
| 6046 | 22 | | GA | | 3-7 | 29-11-22 | D41776J | 29 | | | TB0207Y | A024 | BJ | | 115-199 |
| 6047 | 22 | | GA | | 4-1 | 29-11-22 | D41776J | 30 | | | TB0207Z | 14 | BJ | | 001, 003-099 |
| 6047 | 22 | | GA | | 4-2 | 29-11-22 | D41776J | 30 | | | TB0207Z | 14 | BJ | | 002 |
| 6047 | 22 | | GA | | 4-0 | 29-11-22 | D41776J | 30 | | | TB0207Z | 14 | BJ | | 115-199 |
| 6048 | 24 | | GK | | 3-7 | 26-11-11 | D00321D | G06 | | | D41764J | 21 | | *S | 001-099 |
| 6048 | 24 | | GK | | 4-10 | 26-11-11 | D00321D | G06 | | | D41764J | 28 | | *S | 115-199 |
| 6049 | 24 | | GK | | 2-9 | 26-11-11 | D00319D | G06 | | | D41764J | 21 | | *S | 001-099 |
| 6049 | 24 | | GK | | 3-6 | 26-11-11 | D00319D | G06 | | | D41764J | 28 | | *S | 115-199 |
| 6051 | 24 | | GK | | 3-3 | 26-11-22 | D00319D | G05 | | | D41776J | 6 | | *V | 001-099 |
| 6051 | 24 | | GK | | 3-2 | 26-11-22 | D00319D | G05 | | | D41776J | 6 | | *V | 115-199 |
| 6052 | 24 | | GK | | 3-6 | 26-11-22 | D00321D | G05 | | | D41776J | 6 | | *V | ALL |
| 6054 | 24 | | GK | | 2-10 | 26-16-11 | D00321B | G05 | | | D41738J | 47 | | *R | 001-099 |
| 6054 | 24 | | GK | | 2-11 | 26-16-11 | D00321B | G05 | | | D41738J | 47 | | *R | 115-199 |
| 6055 | 24 | | GK | | 4-1 | 26-16-11 | D00319B | G05 | | | D41738J | 47 | | *R | 001-099 |
| 6055 | 24 | | GK | | 4-2 | 26-16-11 | D00319B | G05 | | | D41738J | 47 | | *R | 115-199 |
| 6057 | 24 | | GK | | 3-7 | 26-16-11 | D00321A | H06 | | | D41736J | 35 | | *Q | ALL |
| 6058 | 24 | | GK | | 3-2 | 26-16-11 | D00319A | H06 | | | D41736J | 35 | | *Q | 001-099 |
| 6058 | 24 | | GK | | 3-3 | 26-16-11 | D00319A | H06 | | | D41736J | 35 | | *Q | 115-199 |
| 6060 | 24 | | GK | | 3-5 | 26-16-11 | D00321E | G02 | | | D41776J | 35 | | *V | ALL |
| 6061 | 24 | | GK | | 3-2 | 26-16-11 | D00319E | G02 | | | D41776J | 35 | | *V | 001-099 |
| 6061 | 24 | | GK | | 3-1 | 26-16-11 | D00319E | G02 | | | D41776J | 35 | | *V | 115-199 |
| 6063 | 24 | | GK | | 3-3 | 26-16-11 | D00321D | F01 | | | D41734J | 40 | | *P | ALL |
| 6064 | 24 | | GK | | 3-0 | 26-16-11 | D00319D | F01 | | | D41734J | 40 | | *P | 001-099 |
| 6064 | 24 | | GK | | 2-11 | 26-16-11 | D00319D | F01 | | | D41734J | 40 | | *P | 115-199 |
| 6066 | 24 | | GK | | 3-6 | 26-16-11 | D00321D | F07 | | | D41776J | 34 | | *V | ALL |
| 6067 | 24 | | GK | | 3-3 | 26-16-11 | D00319D | F07 | | | D41776J | 34 | | *V | 001-099 |
| 6067 | 24 | | GK | | 3-2 | 26-16-11 | D00319D | F07 | | | D41776J | 34 | | *V | 115-199 |
| 6069 | 24 | | GK | | 2-10 | 26-16-11 | D00321F | F07 | | | D41738J | 46 | | *R | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 143

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-----|------------------------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | |
| 6069 | 24 | | GK | | 2-11 | 26-16-11 | D00321F | F07 | | | D41738J | 46 | | *R | 115-199 |
| 6070 | 24 | | GK | | 4-0 | 26-16-11 | D00319F | F07 | | | D41738J | 46 | | *R | ALL |
| 6072 | 18 | | GA | | 4-6 | 73-21-12 | D41772J | 7 | 18 | | TB0207G | 115 | 2 | | 001, 003-099 |
| 6072 | 18 | | GA | | 4-7 | 73-21-12 | D41772J | 7 | 18 | | TB0207G | 115 | 2 | | 002 |
| 6072 | 18 | | GA | | 5-2 | 73-21-12 | D41772J | 23 | 18 | | TB0207G | 115 | 2 | | 115-199 |
| 6073 | 18 | | GA | | 2-4 | 73-21-12 | D41738J | 30 | 18 | | TB0207G | 115 | 2 | | 001, 003-099 |
| 6073 | 18 | | GA | | 2-5 | 73-21-12 | D41738J | 30 | 18 | | TB0207G | 115 | 2 | | 002 |
| 6073 | 18 | | GA | | 2-6 | 73-21-12 | D41738J | 30 | 18 | | TB0207G | 115 | 2 | | 115-199 |
| 6074 | 24 | | GK | | 3-8 | 73-21-12 | D41879J | 48 | | | TB0207G | 115 | 2 | | 001, 003-099 |
| 6074 | 24 | | GK | | 3-9 | 73-21-12 | D41879J | 48 | | | TB0207G | 115 | 2 | | 002, 115-199 |
| 6075 | 18 | | GA | | 4-6 | 73-21-22 | D41788J | 19 | 18 | | TB0207G | 116 | 2 | | 001, 003-099 |
| 6075 | 18 | | GA | | 4-7 | 73-21-22 | D41788J | 19 | 18 | | TB0207G | 116 | 2 | | 002 |
| 6075 | 18 | | GT | JP | 2-8 | 73-21-22 | D41788J | 19 | 18 | | TB0207G | 116 | 2 | | 115-199 |
| 6075Z | | | | JP | 0-0 | 73-21-22 | D41788J | DED | | | TB0207G | DED | | | 115-199 |
| 6076 | 18 | | GA | | 3-2 | 73-21-22 | D41776J | 18 | 18 | | TB0207G | 116 | 2 | | 001, 003-099 |
| 6076 | 18 | | GA | | 3-3 | 73-21-22 | D41776J | 18 | 18 | | TB0207G | 116 | 2 | | 002 |
| 6076 | 18 | | GT | JQ | 3-3 | 73-21-22 | D41776J | 18 | 18 | | TB0207G | 116 | 2 | | 115-199 |
| 6076Z | | | | JQ | 0-0 | 73-21-22 | D41776J | DED | | | TB0207G | DED | | | 115-199 |
| 6077 | 24 | | GK | | 3-2 | 73-21-22 | D41776J | 19 | | | TB0207G | 116 | 2 | | 001, 003-099 |
| 6077 | 24 | | GK | | 3-3 | 73-21-22 | D41776J | 19 | | | TB0207G | 116 | 2 | | 002 |
| 6077 | 24 | | G1 | JR | 3-3 | 73-21-22 | D41776J | 19 | | | TB0207G | 116 | 2 | | 115-199 |
| 6077Z | | | | JR | 0-0 | 73-21-22 | D41776J | DED | | | TB0207G | DED | | | 115-199 |
| 6079 | 24 | | GK | | 3-5 | 26-16-21 | D00321F | E07 | | | D42185J | 24 | | *O | 001-099 |
| 6079 | 24 | | GK | | 3-5 | 26-16-21 | D00321F | E07 | | | D42185J | 24 | | *1 | 115-199 |
| 6080 | 24 | | GK | | 2-6 | 26-16-21 | D00319F | E07 | | | D42185J | 24 | | *O | 001-099 |
| 6080 | 24 | | GK | | 2-6 | 26-16-21 | D00319F | E07 | | | D42185J | 24 | | *1 | 115-199 |
| 6090 | 24 | | GK | | 4-3 | 26-23-11 | D00319D | D01 | | | D41738J | 48 | | *R | ALL |
| 6091 | 24 | | GK | | 3-1 | 26-23-11 | D00321D | D01 | | | D41738J | 48 | | *R | 001-099 |
| 6091 | 24 | | GK | | 3-2 | 26-23-11 | D00321D | D01 | | | D41738J | 48 | | *R | 115-199 |
| 6093 | 24 | | GK | | 4-0 | 26-23-11 | D00319F | C08 | | | D41738J | 49 | | *R | ALL |
| 6094 | 24 | | GK | | 2-10 | 26-23-11 | D00321F | C08 | | | D41738J | 49 | | *R | 001-099 |
| 6094 | 24 | | GK | | 2-11 | 26-23-11 | D00321F | C08 | | | D41738J | 49 | | *R | 115-199 |
| 6095 | 22 | | GA | | 3-8 | 27-18-11 | D41698J | 8 | | | D40684J | 10 | | | 001-099 |
| 6095 | 24 | | GK | | 3-6 | 27-18-11 | D40684J | 10 | | | D41698J | 8 | | | 115-199 |
| 6097 | 22 | | GA | | 1-11 | 27-18-11 | D41720J | 15 | | | D40704J | 10 | | | 001-099 |
| 6097 | 22 | | GA | | 1-10 | 27-18-11 | D41720J | 15 | | | D40704J | 10 | | | 115-199 |
| 6098 | 24 | | GK | | 2-7 | 31-41-14 | D00319A | K01 | | | D00755 | 21 | VP | | 001-010 |
| 6098 | 24 | | GK | | 2-10 | 31-41-14 | D00319A | K01 | | | D00755 | 21 | VP | | 011-099 |
| 6098 | 24 | | GK | | 2-8 | 31-41-14 | D00319A | K01 | | | D00755 | 21 | VP | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 144

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6099 | 24 | | GK | | 2-7 | 31-41-14 | D00319A | | K09 | | D00755 | 22 | VP | | 001-010 |
| 6099 | 24 | | GK | | 2-10 | 31-41-14 | D00319A | | K09 | | D00755 | 22 | VP | | 011-099 |
| 6099 | 24 | | GK | | 2-8 | 31-41-14 | D00319A | | K09 | | D00755 | 22 | VP | | 115-199 |
| 6100 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | | K09 | | D00755 | 23 | VP | | 001-010, 115-199 |
| 6100 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | | K09 | | D00755 | 23 | VP | | 011-099 |
| 6101 | 24 | | GK | | 2-6 | 31-41-14 | D00319B | | K06 | | D00755 | 24 | VP | | 001-010, 115-199 |
| 6101 | 24 | | GK | | 2-9 | 31-41-14 | D00319B | | K06 | | D00755 | 24 | VP | | 011-099 |
| 6102 | 24 | | GK | | 2-7 | 31-41-14 | D00319D | | K12 | | D00755 | 25 | VP | | 001-010 |
| 6102 | 24 | | GK | | 2-9 | 31-41-14 | D00319D | | K12 | | D00755 | 25 | VP | | 011-099 |
| 6102 | 24 | | GK | | 2-8 | 31-41-14 | D00319D | | K12 | | D00755 | 25 | VP | | 115-199 |
| 6103 | 24 | | GK | | 2-7 | 31-41-14 | D00319D | | J12 | | D00755 | 26 | VP | | 001-010 |
| 6103 | 24 | | GK | | 2-9 | 31-41-14 | D00319D | | J12 | | D00755 | 26 | VP | | 011-099 |
| 6103 | 24 | | GK | | 2-8 | 31-41-14 | D00319D | | J12 | | D00755 | 26 | VP | | 115-199 |
| 6104 | 24 | | GK | | 2-5 | 31-41-14 | D00319E | | K01 | | D00755 | 27 | VP | | 001-010 |
| 6104 | 24 | | GK | | 2-8 | 31-41-14 | D00319E | | K01 | | D00755 | 27 | VP | | 011-099 |
| 6104 | 24 | | GK | | 2-6 | 31-41-14 | D00319E | | K01 | | D00755 | 27 | VP | | 115-199 |
| 6105 | 24 | | GK | | 2-5 | 31-41-14 | D00319E | | J08 | | D00755 | 28 | VP | | 001-010 |
| 6105 | 24 | | GK | | 2-8 | 31-41-14 | D00319E | | J08 | | D00755 | 28 | VP | | 011-099 |
| 6105 | 24 | | GK | | 2-6 | 31-41-14 | D00319E | | J08 | | D00755 | 28 | VP | | 115-199 |
| 6106 | 24 | | GK | | 2-5 | 31-41-14 | D00319E | | J04 | | D00755 | 31 | VP | | 001-010 |
| 6106 | 24 | | GK | | 2-8 | 31-41-14 | D00319E | | J04 | | D00755 | 31 | VP | | 011-099 |
| 6106 | 24 | | GK | | 2-6 | 31-41-14 | D00319E | | J04 | | D00755 | 31 | VP | | 115-199 |
| 6107 | 24 | | GK | | 2-5 | 31-41-14 | D00319E | | J01 | | D00755 | 32 | VJ | | 001-010 |
| 6107 | 24 | | GK | | 2-8 | 31-41-14 | D00319E | | J01 | | D00755 | 32 | VJ | | 011-099 |
| 6107 | 24 | | GK | | 2-6 | 31-41-14 | D00319E | | J01 | | D00755 | 32 | | | 115-199 |
| 6108 | 24 | | GK | | 2-4 | 31-41-14 | D00319F | | J05 | | D00755 | 29 | VP | | 001-010 |
| 6108 | 24 | | GK | | 2-6 | 31-41-14 | D00319F | | J05 | | D00755 | 29 | VP | | 011-099 |
| 6108 | 24 | | GK | | 2-5 | 31-41-14 | D00319F | | J05 | | D00755 | 29 | VP | | 115-199 |
| 6109 | 24 | | GK | | 2-4 | 31-41-14 | D00319F | | H05 | | D00755 | 30 | VJ | | 001-010 |
| 6109 | 24 | | GK | | 2-6 | 31-41-14 | D00319F | | H05 | | D00755 | 30 | VJ | | 011-099 |
| 6109 | 24 | | GK | | 2-5 | 31-41-14 | D00319F | | H05 | | D00755 | 30 | | | 115-199 |
| 6110 | 24 | | GK | | 2-8 | 31-41-24 | D00321A | | K01 | | D00757 | 21 | VP | | 001-010 |
| 6110 | 24 | | GK | | 2-11 | 31-41-24 | D00321A | | K01 | | D00757 | 21 | VP | | 011-099 |
| 6110 | 24 | | GK | | 2-9 | 31-41-24 | D00321A | | K01 | | D00757 | 21 | VP | | 115-199 |
| 6111 | 24 | | GK | | 2-8 | 31-41-24 | D00321A | | K09 | | D00757 | 22 | VP | | 001-010 |
| 6111 | 24 | | GK | | 2-11 | 31-41-24 | D00321A | | K09 | | D00757 | 22 | VP | | 011-099 |
| 6111 | 24 | | GK | | 2-9 | 31-41-24 | D00321A | | K09 | | D00757 | 22 | VP | | 115-199 |
| 6112 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | | K09 | | D00757 | 23 | VP | | 001-010 |
| 6112 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | | K09 | | D00757 | 23 | VP | | 011-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 145

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6112 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | | K09 | | | D00757 | 23 | VP | | 115-199 |
| 6113 | 24 | | GK | | 2-7 | 31-41-24 | D00321B | | K06 | | | D00757 | 24 | VP | | 001-010 |
| 6113 | 24 | | GK | | 2-10 | 31-41-24 | D00321B | | K06 | | | D00757 | 24 | VP | | 011-099 |
| 6113 | 24 | | GK | | 2-8 | 31-41-24 | D00321B | | K06 | | | D00757 | 24 | VP | | 115-199 |
| 6114 | 24 | | GK | | 2-7 | 31-41-24 | D00321D | | K12 | | | D00757 | 25 | VP | | 001-010 |
| 6114 | 24 | | GK | | 2-10 | 31-41-24 | D00321D | | K12 | | | D00757 | 25 | VP | | 011-099 |
| 6114 | 24 | | GK | | 2-8 | 31-41-24 | D00321D | | K12 | | | D00757 | 25 | VP | | 115-199 |
| 6115 | 24 | | GK | | 2-7 | 31-41-24 | D00321D | | J12 | | | D00757 | 26 | VP | | 001-010 |
| 6115 | 24 | | GK | | 2-10 | 31-41-24 | D00321D | | J12 | | | D00757 | 26 | VP | | 011-099 |
| 6115 | 24 | | GK | | 2-8 | 31-41-24 | D00321D | | J12 | | | D00757 | 26 | VP | | 115-199 |
| 6116 | 24 | | GK | | 2-6 | 31-41-24 | D00321E | | K01 | | | D00757 | 27 | VP | | 001-010 |
| 6116 | 24 | | GK | | 2-9 | 31-41-24 | D00321E | | K01 | | | D00757 | 27 | VP | | 011-099 |
| 6116 | 24 | | GK | | 2-7 | 31-41-24 | D00321E | | K01 | | | D00757 | 27 | VP | | 115-199 |
| 6117 | 24 | | GK | | 2-6 | 31-41-24 | D00321E | | J08 | | | D00757 | 28 | VP | | 001-010 |
| 6117 | 24 | | GK | | 2-9 | 31-41-24 | D00321E | | J08 | | | D00757 | 28 | VP | | 011-099 |
| 6117 | 24 | | GK | | 2-7 | 31-41-24 | D00321E | | J08 | | | D00757 | 28 | VP | | 115-199 |
| 6118 | 24 | | GK | | 2-6 | 31-41-24 | D00321E | | J04 | | | D00757 | 31 | VP | | 001-010 |
| 6118 | 24 | | GK | | 2-9 | 31-41-24 | D00321E | | J04 | | | D00757 | 31 | VP | | 011-099 |
| 6118 | 24 | | GK | | 2-7 | 31-41-24 | D00321E | | J04 | | | D00757 | 31 | VP | | 115-199 |
| 6119 | 24 | | GK | | 2-6 | 31-41-24 | D00321E | | J01 | | | D00757 | 32 | VP | | 001-010 |
| 6119 | 24 | | GK | | 2-9 | 31-41-24 | D00321E | | J01 | | | D00757 | 32 | VP | | 011-099 |
| 6119 | 24 | | GK | | 2-7 | 31-41-24 | D00321E | | J01 | | | D00757 | 32 | VP | | 115-199 |
| 6120 | 24 | | GK | | 2-4 | 31-41-24 | D00321F | | J05 | | | D00757 | 29 | VP | | 001-010 |
| 6120 | 24 | | GK | | 2-7 | 31-41-24 | D00321F | | J05 | | | D00757 | 29 | VP | | 011-099 |
| 6120 | 24 | | GK | | 2-5 | 31-41-24 | D00321F | | J05 | | | D00757 | 29 | VP | | 115-199 |
| 6121 | 24 | | GK | | 2-4 | 31-41-24 | D00321F | | H05 | | | D00757 | 30 | VJ | | 001-010 |
| 6121 | 24 | | GK | | 2-7 | 31-41-24 | D00321F | | H05 | | | D00757 | 30 | VJ | | 011-099 |
| 6121 | 24 | | GK | | 2-5 | 31-41-24 | D00321F | | H05 | | | D00757 | 30 | VJ | | 115-199 |
| 6122 | 24 | | GK | | 2-11 | 31-51-41 | D00319A | | H15 | | | D41317J | 7 | | | 001, 003-099 |
| 6122 | 24 | | GK | | 2-11 | 31-51-41 | D00319A | | H15 | | | TB0207Y | A040 | BJ | | 002 |
| 6122 | 24 | | GK | | 3-0 | 31-51-41 | D00319A | | H15 | | | D41317J | 7 | | | 115-199 |
| 6123 | 24 | | GK | | 5-4 | 31-51-41 | D00321A | | H15 | | | D41867J | 18 | | | 001, 003-099 |
| 6123 | 24 | | GK | | 5-4 | 31-51-41 | D00321A | | H15 | | | TB0207Y | C049 | BJ | | 002 |
| 6123 | 24 | | G1 | JK | 5-5 | 31-51-41 | D00321A | | H15 | | | D41867J | 18 | | | 115-199 |
| 6123Z | | | | JK | 0-0 | 31-51-41 | D00321A | | DED | | | D41867J | DED | | | 115-199 |
| 6126 | 24 | | GK | | 2-11 | SPARE | D00319D | | C15 | | | D41317J | 45 | | *F | 001-099 |
| 6127 | 24 | | GK | | 4-3 | SPARE | D00321D | | C15 | | | D41317J | 45 | | *F | 001-099 |
| 6135 | 24 | | GK | | 2-9 | 27-23-11 | D00321F | | K08 | | | D41451J | 3 | | *H | ALL |
| 6136 | 24 | | GK | | 3-6 | 27-23-11 | D00319F | | K08 | | | D41451J | 3 | | *H | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 146

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6138 | 24 | | GK | | 3-5 | 27-23-11 | D00321D | | H02 | | D41632J | 7 | | *1 | ALL |
| 6139 | 24 | | GK | | 3-1 | 27-23-11 | D00319D | | H02 | | D41632J | 7 | | *1 | ALL |
| 6141 | 24 | | GK | | 2-7 | 27-23-11 | D00319A | | H09 | | D41628J | 32 | | *J | 001-099 |
| 6141 | 24 | | GK | | 2-8 | 27-23-11 | D00319A | | H09 | | D41628J | 32 | | *J | 115-199 |
| 6142 | 24 | | GK | | 3-7 | 27-23-11 | D00321A | | H09 | | D41628J | 32 | | *J | 001-099 |
| 6142 | 24 | | GK | | 3-8 | 27-23-11 | D00321A | | H09 | | D41628J | 32 | | *J | 115-199 |
| 6144 | 24 | | GK | | 2-5 | 27-23-11 | D00319B | | H09 | | D41628J | 31 | | *J | 001-099 |
| 6144 | 24 | | GK | | 2-7 | 27-23-11 | D00319B | | H09 | | D41628J | 31 | | *J | 115-199 |
| 6145 | 24 | | GK | | 3-6 | 27-23-11 | D00321B | | H09 | | D41628J | 31 | | *J | ALL |
| 6147 | 24 | | GK | | 3-5 | 27-23-11 | D00321D | | K04 | | D41632J | 8 | | *1 | ALL |
| 6148 | 24 | | GK | | 3-1 | 27-23-11 | D00319D | | K04 | | D41632J | 8 | | *1 | ALL |
| 6150 | 24 | | GK | | 3-6 | 27-23-11 | D00319F | | J06 | | D41451J | 2 | | *H | ALL |
| 6151 | 24 | | GK | | 2-9 | 27-23-11 | D00321F | | J06 | | D41451J | 2 | | *H | ALL |
| 6153 | 22 | | GA | | 2-11 | 27-28-13 | D40684J | | 1 | | TB0207Y | C047 | BJ | | 001-099 |
| 6153 | 24 | | GK | | 2-9 | 27-28-13 | D40684J | | 1 | | TB0207Y | C047 | BJ | | 115-199 |
| 6154 | 22 | | GA | | 3-11 | 27-28-13 | D40584J | | 4 | | TB0207Y | C047 | BJ | | 001-099 |
| 6154 | 24 | | GK | | 4-0 | 27-28-13 | D40584J | | 4 | | TB0207Y | C047 | BJ | | 115-199 |
| 6155 | 22 | | GA | | 2-6 | 27-28-13 | D41628J | | 26 | | TB0207Y | C047 | BJ | | 001-099 |
| 6155 | 24 | | GK | | 2-7 | 27-28-13 | D41628J | | 26 | | TB0207Y | C047 | BJ | | 115-199 |
| 6156 | 22 | | GA | | 3-5 | 27-28-13 | D40584J | | 14 | | D41628J | 27 | | | 001-099 |
| 6156 | 24 | | GK | | 3-7 | 27-28-13 | D41628J | | 27 | | D40584J | 14 | | | 115-199 |
| 6157 | 24 | | GK | | 2-11 | 27-58-11 | D42073J | | 6 | | D41317J | 49 | | | 001-099 |
| 6157 | 22 | | GA | | 3-1 | 27-58-11 | D42073J | | 6 | | D41317J | 49 | | | 115-199 |
| 6158 | 24 | | GK | | 2-11 | 27-58-11 | D42073J | | 5 | | D41317J | 50 | | | 001-099 |
| 6158 | 22 | | GA | | 3-1 | 27-58-11 | D42073J | | 5 | | D41317J | 50 | | | 115-199 |
| 6159 | 24 | | GK | | 2-11 | 27-58-11 | D42073J | | 4 | | D41317J | 51 | | | 001-099 |
| 6159 | 22 | | GA | | 3-1 | 27-58-11 | D42073J | | 4 | | D41317J | 51 | | | 115-199 |
| 6160 | 24 | | GK | | 2-11 | 27-58-11 | D42073J | | 3 | | D41317J | 52 | | | 001-099 |
| 6160 | 22 | | GA | | 3-1 | 27-58-11 | D42073J | | 3 | | D41317J | 52 | | | 115-199 |
| 6161 | 24 | | GK | | 2-10 | 27-58-31 | D41698J | | 23 | | TB0207Y | C048 | BJ | | ALL |
| 6162 | 24 | | GK | | 3-7 | 27-58-31 | D41409J | | 10 | | TB0207Y | C048 | BJ | | ALL |
| 6163 | 24 | | GK | | 2-7 | 27-58-31 | D00319D | | F03 | | TB0207Y | C048 | BJ | | 001-099 |
| 6163 | 24 | | GK | | 2-8 | 27-58-31 | D00319D | | F03 | | TB0207Y | C048 | BJ | | 115-199 |
| 6164 | 24 | | GK | | 4-0 | 27-58-31 | D00321D | | F03 | | TB0207Y | C048 | BJ | | ALL |
| 6166 | 24 | | GK | | 3-8 | 27-58-31 | D00319D | | C14 | | D41409J | 4 | | *U | 001-099 |
| 6166 | 24 | | GK | | 3-7 | 27-58-31 | D00319D | | C14 | | D41409J | 4 | | *1 | 115-199 |
| 6167 | 24 | | GK | | 2-11 | 27-58-31 | D00321D | | C14 | | D41409J | 4 | | *U | 001-099 |
| 6167 | 24 | | GK | | 2-11 | 27-58-31 | D00321D | | C14 | | D41409J | 4 | | *1 | 115-199 |
| 6168 | 24 | | GK | | 3-7 | 26-16-21 | D00321D | | G11 | | D42185J | 22 | | *O | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 147

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6168 | 24 | | GK | | 3-8 | 26-16-21 | D00321D | | G11 | | D42185J | 22 | | *1 | 115-199 |
| 6169 | 24 | | GK | | 2-9 | 26-16-21 | D00319D | | G11 | | D42185J | 22 | | *O | 001-099 |
| 6169 | 24 | | GK | | 2-9 | 26-16-21 | D00319D | | G11 | | D42185J | 22 | | *1 | 115-199 |
| 6170 | 24 | | GK | | 3-6 | 26-16-21 | D00321E | | C11 | | D42185J | 23 | | *O | 001-099 |
| 6170 | 24 | | GK | | 3-7 | 26-16-21 | D00321E | | C11 | | D42185J | 23 | | *1 | 115-199 |
| 6171 | 24 | | GK | | 2-7 | 26-16-21 | D00319E | | C11 | | D42185J | 23 | | *O | 001-099 |
| 6171 | 24 | | GK | | 2-8 | 26-16-21 | D00319E | | C11 | | D42185J | 23 | | *1 | 115-199 |
| 6172 | 22 | | GA | | 1-10 | 29-11-31 | D41409J | | 6 | | D40214J | 4 | | | 001, 003-099 |
| 6172 | 22 | | GA | | 1-11 | 29-11-31 | D41409J | | 6 | | D40214J | 4 | | | 002, 115-199 |
| 6173 | 22 | | GA | | 2-8 | 29-11-31 | D41409J | | 5 | | TB0207Z | 105 | BJ | | 001-099 |
| 6173 | 22 | | GA | | 2-7 | 29-11-31 | D41409J | | 5 | | TB0207Z | 105 | BJ | | 115-199 |
| 6174 | 22 | | GA | | 3-0 | 29-11-12 | D41867J | | 12 | | TB0207Y | C026 | BJ | | 001-099 |
| 6174 | 22 | | GA | | 5-0 | 29-11-12 | D41867J | | 12 | | TB0207Z | 103 | BJ | | 115-199 |
| 6175 | 22 | | GA | | 3-9 | 29-11-22 | D41879J | | 29 | | TB0207Z | 104 | BJ | | ALL |
| 6176 | 22 | | GA | | 3-7 | 32-44-11 | D41736J | | 47 | | TB0207Y | C027 | BJ | | 001, 003-099 |
| 6176 | 22 | | GA | | 3-8 | 32-44-11 | D41736J | | 47 | | TB0207Y | C027 | BJ | | 002 |
| 6176 | 22 | | GA | | 3-8 | 32-44-11 | D41788J | | 7 | | D41734J | 51 | | | 115-199 |
| 6177 | 24 | | GK | | 2-4 | 32-41-11 | D00319E | | H12 | | TB0207Y | A051 | BJ | | 001-099 |
| 6177 | 24 | | GK | | 2-5 | 32-41-11 | D00319E | | H12 | | TB0207Y | A051 | BJ | | 115-199 |
| 6178 | 24 | | GK | | 3-5 | 32-41-11 | D00321E | | H12 | | TB0207Y | A051 | BJ | | 001, 003-099 |
| 6178 | 24 | | GK | | 3-6 | 32-41-11 | D00321E | | H12 | | TB0207Y | A051 | BJ | | 002 |
| 6178 | 24 | | GK | | 3-7 | 32-41-11 | D00321E | | H12 | | TB0207Y | A051 | BJ | | 115-199 |
| 6179 | 24 | | GK | | 2-9 | 32-41-11 | D41736J | | 37 | | TB0207Y | A051 | BJ | | 001-099 |
| 6179 | 24 | | GK | | 2-10 | 32-41-11 | D41736J | | 37 | | TB0207Y | A051 | BJ | | 115-199 |
| 6180 | 24 | | GK | | 3-3 | 32-41-11 | D41451J | | 55 | | TB0207Y | A051 | BJ | | 001-099 |
| 6180 | 24 | | GK | | 2-7 | 32-41-11 | D41664J | | 21 | | TB0207Y | A051 | BJ | | 115-199 |
| 6181 | 22 | | GA | | 3-0 | 22-41-11 | D41867J | | 20 | | TB0207Y | A027 | BJ | | 001-099 |
| 6181 | 22 | | GA | | 3-1 | 22-41-11 | D41867J | | 20 | | TB0207Z | 28 | BJ | | 115-199 |
| 6182 | 22 | | GA | | 2-7 | 22-41-11 | D41879J | | 27 | | TB0207Y | A024 | BJ | | 001, 003-099, 115-199 |
| 6182 | 22 | | GA | | 2-8 | 22-41-11 | D41879J | | 27 | | TB0207Y | A024 | BJ | | 002 |
| 6183 | 22 | | GA | | 5-0 | 22-41-11 | D41867J | | 21 | | TB0207Z | 105 | BJ | | ALL |
| 6184 | 22 | | GA | | 2-5 | 27-23-11 | D41698J | | 14 | | TB0207Y | A060 | BJ | | 001-099 |
| 6184 | 22 | | GA | | 2-7 | 27-23-11 | D41698J | | 14 | | TB0207Y | A060 | BJ | | 115-199 |
| 6185 | 20 | | GA | | 2-9 | 29-31-11 | D41794J | | 6 | | GD02201 | AC.. | 2 | | ALL |
| 6186 | 20 | | GA | | 3-4 | 29-31-11 | D41792J | | 2 | | GD02204 | AC.. | 2 | | 001-099 |
| 6186 | 20 | | GA | | 3-5 | 29-31-11 | D41792J | | 14 | | GD02204 | AC.. | 2 | | 115-199 |
| 6187 | 20 | | GA | | 2-8 | 29-31-11 | D41698J | | 17 | | GD02207 | AC.. | 2 | | 001-099 |
| 6187 | 20 | | GA | | 2-11 | 29-31-11 | D41698J | | 17 | | GD02207 | AC.. | 2 | | 115-199 |
| 6188 | 24 | | GK | | 4-0 | 21-61-51 | D00319D | | A13 | | D40584J | 11 | | *C | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 148

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6189 | 24 | | GK | | 2-10 | 21-61-51 | D00321D | A13 | | | D40584J | 11 | | *C | 001-099 |
| 6189 | 24 | | GK | | 2-11 | 21-61-51 | D00321D | A13 | | | D40584J | 11 | | *C | 115-199 |
| 6190 | 24 | | GK | | 2-7 | 22-34-11 | D00319B | D08 | | | D41879J | 4 | | *Z | ALL |
| 6191 | 24 | | GK | | 4-0 | 22-34-11 | D00321B | D08 | | | D41879J | 4 | | *Z | ALL |
| 6192 | 24 | | GK | | 2-9 | 21-52-21 | D42086J | 13 | | | GD02205 | DC.. | 2 | | 001-099 |
| 6192 | 24 | | GK | | 2-5 | 21-52-21 | D42086J | 13 | | | GD02205 | DC.. | 2 | | 115-199 |
| 6193 | 24 | | GK | | 2-9 | 21-52-21 | D42086J | 14 | | | GD02205 | DC.. | 2 | | 001-099 |
| 6193 | 24 | | GK | | 2-5 | 21-52-21 | D42086J | 14 | | | GD02205 | DC.. | 2 | | 115-199 |
| 6194 | 24 | | GK | | 2-7 | 21-52-21 | D42084J | 13 | | | GD02201 | DC.. | 2 | | 001-099 |
| 6194 | 24 | | GK | | 2-8 | 21-52-21 | D42084J | 13 | | | GD02202 | DC.. | 2 | | 115-199 |
| 6195 | 24 | | GK | | 2-7 | 21-52-21 | D42084J | 14 | | | GD02201 | DC.. | 2 | | 001-099 |
| 6195 | 24 | | GK | | 2-8 | 21-52-21 | D42084J | 14 | | | GD02202 | DC.. | 2 | | 115-199 |
| 6196 | 24 | | GK | | 3-1 | 21-52-31 | D04646B | B14 | | | D40684J | 14 | | | 001-099 |
| 6196 | 24 | | GK | | 3-0 | 21-52-31 | D04646B | B14 | | | D40684J | 14 | | | 115-199 |
| 6197 | 24 | | GK | | 3-4 | 21-52-31 | D04646B | A15 | | | GD02203 | AC.. | 2 | | 001-099 |
| 6197 | 24 | | GK | | 2-8 | 21-52-31 | D04646B | A15 | | | GD02202 | AC.. | 2 | | 115-199 |
| 6198 | 24 | | GK | | 5-5 | 21-52-31 | D04646A | A01 | | | D00321E | E02 | | | 001-099 |
| 6198 | 24 | | GK | | 5-4 | 21-52-31 | D00321E | E02 | | | D04646A | A01 | | | 115-199 |
| 6199 | 24 | | GK | | 3-5 | 21-52-31 | D04646A | A02 | | | GD02203 | DC.. | 2 | | 001-099 |
| 6199 | 24 | | GK | | 2-9 | 21-52-31 | D04646A | A02 | | | GD02202 | DC.. | 2 | | 115-199 |
| 6200 | 24 | | GK | | 3-5 | 21-52-31 | D04646A | D15 | | | GD02203 | ST.. | 2 | | 001-099 |
| 6200 | 24 | | GK | | 2-9 | 21-52-31 | D04646A | D15 | | | GD02202 | ST.. | 2 | | 115-199 |
| 6201 | 24 | | GK | | 3-11 | 21-52-31 | D04646B | A01 | | | D00319E | E02 | | | 001-099 |
| 6201 | 24 | | GK | | 3-11 | 21-52-31 | D00319E | E02 | | | D04646B | A01 | | | 115-199 |
| 6202 | 24 | | GK | | 2-9 | 21-52-31 | D04646B | A02 | | | GD02202 | DC.. | 2 | | 001-099 |
| 6202 | 24 | | GK | | 2-8 | 21-52-31 | D04646B | A02 | | | GD02202 | DC.. | 2 | | 115-199 |
| 6203 | 24 | | GK | | 2-10 | 21-64-11 | D42086J | 44 | | | TB0207Z | 74 | BJ | | 001, 003-099 |
| 6203 | 24 | | GK | | 2-11 | 21-64-11 | D42086J | 44 | | | TB0207Z | 74 | BJ | | 002 |
| 6203 | 24 | | GK | | 3-8 | 21-64-11 | D42086J | 44 | | | TB0207Z | 74 | BJ | | 115-199 |
| 6204 | 24 | | GK | | 2-5 | 21-64-11 | D42086J | 45 | | | D00319F | G09 | | | 001-099 |
| 6204 | 24 | | GK | | 3-1 | 21-64-11 | D00319F | G09 | | | D42086J | 45 | | | 115-199 |
| 6205 | 24 | | GK | | 2-9 | 21-64-11 | D42086J | 46 | | | GD02205 | DC.. | 2 | | 001-099 |
| 6205 | 24 | | GK | | 2-5 | 21-64-11 | D42086J | 46 | | | GD02205 | DC.. | 2 | | 115-199 |
| 6206 | 24 | | GK | | 2-9 | 21-64-11 | D42086J | 49 | | | GD02205 | DC.. | 2 | | 001-099 |
| 6206 | 24 | | GK | | 2-5 | 21-64-11 | D42086J | 49 | | | GD02205 | DC.. | 2 | | 115-199 |
| 6207 | 24 | | GK | | 2-9 | 21-64-11 | D42086J | 43 | | | GD02205 | DC.. | 2 | | 001-099 |
| 6207 | 24 | | GK | | 2-5 | 21-64-11 | D42086J | 43 | | | GD02205 | DC.. | 2 | | 115-199 |
| 6208 | 24 | | GK | | 2-9 | 36-21-11 | D42086J | 25 | | | GD02205 | DC.. | 2 | | 001-099 |
| 6208 | 24 | | GK | | 2-5 | 36-21-11 | D42086J | 25 | | | GD02205 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 149

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6209 | 24 | | GK | | 2-6 | 36-21-11 | D42084J | 25 | | | GD02202 | DC.. | 2 | | 001-099 |
| 6209 | 24 | | GK | | 2-8 | 36-21-11 | D42084J | 25 | | | GD02202 | DC.. | 2 | | 115-199 |
| 6210 | 24 | | GK | | 3-9 | 36-21-11 | D42084J | 24 | | | D00319D | H13 | | | 001-099 |
| 6210 | 24 | | G1 | BL | 4-0 | 36-21-11 | D00319D | H13 | | | D42084J | 24 | | | 115-199 |
| 6210Z | | | | BL | 0-0 | 36-21-11 | D00319D | DED | | | D42084J | DED | | | 115-199 |
| 6211 | 24 | | GK | | 4-0 | 36-21-11 | D42086J | 24 | | | D00321D | H13 | | | 001-099 |
| 6211 | 24 | | G1 | JL | 4-7 | 36-21-11 | D00321D | H13 | | | D42086J | 24 | | | 115-199 |
| 6211Z | | | | JL | 0-0 | 36-21-11 | D00321D | DED | | | D42086J | DED | | | 115-199 |
| 6218 | 24 | | GK | | 2-10 | 21-64-11 | D42086J | 41 | | | TB0207Z | 74 | BJ | | 001, 003-099 |
| 6218 | 24 | | GK | | 2-11 | 21-64-11 | D42086J | 41 | | | TB0207Z | 74 | BJ | | 002 |
| 6218 | 24 | | GK | | 3-8 | 21-64-11 | D42086J | 41 | | | TB0207Z | 74 | BJ | | 115-199 |
| 6219 | 24 | | GK | | 2-10 | 21-64-11 | D42086J | 47 | | | TB0207Z | 74 | BJ | | 001, 003-099 |
| 6219 | 24 | | GK | | 2-11 | 21-64-11 | D42086J | 47 | | | TB0207Z | 74 | BJ | | 002 |
| 6219 | 24 | | GK | | 3-8 | 21-64-11 | D42086J | 47 | | | TB0207Z | 74 | BJ | | 115-199 |
| 6220 | 20 | | GA | | 0-7 | 21-64-11 | TB0207Z | 78 | BJ | | TB0207Z | 74 | BJ | | ALL |
| 6221 | 24 | | GK | | 3-9 | 21-64-11 | D42086J | 48 | | | D00321F | B09 | | | 001-099 |
| 6221 | 24 | | GK | | 4-4 | 21-64-11 | D00321F | B09 | | | D42086J | 48 | | | 115-199 |
| 6222 | 24 | | GK | | 2-5 | 21-64-11 | D42086J | 42 | | | D00319F | B09 | | | 001-099 |
| 6222 | 24 | | GK | | 3-1 | 21-64-11 | D00319F | B09 | | | D42086J | 42 | | | 115-199 |
| 6223 | 24 | | GK | | 4-0 | 21-52-21 | D42084J | 11 | | | TB0207Z | 74 | BJ | | 001, 003-099 |
| 6223 | 24 | | GK | | 4-1 | 21-52-21 | D42084J | 11 | | | TB0207Z | 74 | BJ | | 002 |
| 6223 | 24 | | GK | | 4-5 | 21-52-21 | D42084J | 11 | | | TB0207Z | 74 | BJ | | 115-199 |
| 6224 | 24 | | GK | | 2-10 | 21-52-21 | D42086J | 11 | | | TB0207Z | 74 | BJ | | 001, 003-099 |
| 6224 | 24 | | GK | | 2-11 | 21-52-21 | D42086J | 11 | | | TB0207Z | 74 | BJ | | 002 |
| 6224 | 24 | | GK | | 3-8 | 21-52-21 | D42086J | 11 | | | TB0207Z | 74 | BJ | | 115-199 |
| 6225 | 24 | | GK | | 3-11 | 21-52-21 | D42086J | 12 | | | D00321E | H13 | | | 001-099 |
| 6225 | 24 | | GK | | 4-6 | 21-52-21 | D00321E | H13 | | | D42086J | 12 | | | 115-199 |
| 6226 | 24 | | GK | | 3-8 | 21-52-21 | D42084J | 12 | | | D00319E | H13 | | | 001-099 |
| 6226 | 24 | | GK | | 3-11 | 21-52-21 | D00319E | H13 | | | D42084J | 12 | | | 115-199 |
| 6229 | 24 | | GK | | 5-4 | 32-61-12 | D00321A | K06 | | | D41867J | 26 | | *Y | 001-099 |
| 6229 | 24 | | GK | | 5-5 | 32-61-12 | D00321A | K06 | | | D41867J | 26 | | *Y | 115-199 |
| 6230 | 24 | | GK | | 3-11 | 32-61-12 | D00319A | K06 | | | D41867J | 26 | | *Y | 001-099 |
| 6230 | 24 | | GK | | 4-0 | 32-61-12 | D00319A | K06 | | | D41867J | 26 | | *Y | 115-199 |
| 6231 | 24 | | GK | | 5-4 | 32-61-12 | D00321A | D10 | | | D41867J | 27 | | *Y | 001-099 |
| 6231 | 24 | | GK | | 5-5 | 32-61-12 | D00321A | D10 | | | D41867J | 27 | | *Y | 115-199 |
| 6232 | 24 | | GK | | 3-11 | 32-61-12 | D00319A | D10 | | | D41867J | 27 | | *Y | 001-099 |
| 6232 | 24 | | GK | | 4-0 | 32-61-12 | D00319A | D10 | | | D41867J | 27 | | *Y | 115-199 |
| 6233 | 24 | | GK | | 5-4 | 32-61-12 | D00321A | G12 | | | D41867J | 25 | | *Y | 001-099 |
| 6233 | 24 | | GK | | 5-5 | 32-61-12 | D00321A | G12 | | | D41867J | 25 | | *Y | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 150

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|----|-----|------------------------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|--|--|
| Wire No. | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | | |
| 6234 | 24 | | GK | | 3-11 | 32-61-12 | D00319A | | G12 | | D41867J | 25 | | *Y | 001-099 | | |
| 6234 | 24 | | GK | | 4-0 | 32-61-12 | D00319A | | G12 | | D41867J | 25 | | *Y | 115-199 | | |
| 6235 | 24 | | GK | | 4-0 | 32-61-12 | D00321D | | B07 | | D41879J | 34 | | *Z | 001-099 | | |
| 6235 | 24 | | GK | | 4-0 | 32-61-11 | D00321D | | B07 | | D41879J | 34 | | *Z | 115-199 | | |
| 6236 | 24 | | GK | | 2-8 | 32-61-12 | D00319D | | B07 | | D41879J | 34 | | *Z | 001-099 | | |
| 6236 | 24 | | GK | | 2-9 | 32-61-11 | D00319D | | B07 | | D41879J | 34 | | *Z | 115-199 | | |
| 6237 | 24 | | GK | | 4-0 | 32-61-12 | D00321D | | C12 | | D41879J | 9 | | *Z | 001-099 | | |
| 6237 | 24 | | GK | | 4-0 | 32-61-11 | D00321D | | C12 | | D41879J | 9 | | *Z | 115-199 | | |
| 6238 | 24 | | GK | | 2-8 | 32-61-12 | D00319D | | C12 | | D41879J | 9 | | *Z | 001-099 | | |
| 6238 | 24 | | GK | | 2-9 | 32-61-11 | D00319D | | C12 | | D41879J | 9 | | *Z | 115-199 | | |
| 6239 | 24 | | GK | | 3-11 | 32-61-12 | D00321E | | D11 | | D41879J | 33 | | *Z | 001-099 | | |
| 6239 | 24 | | GK | | 3-11 | 32-61-11 | D00321E | | D11 | | D41879J | 33 | | *Z | 115-199 | | |
| 6240 | 24 | | GK | | 2-6 | 32-61-12 | D00319E | | D11 | | D41879J | 33 | | *Z | 001-099 | | |
| 6240 | 24 | | GK | | 2-7 | 32-61-11 | D00319E | | D11 | | D41879J | 33 | | *Z | 115-199 | | |
| 6241 | 24 | | GK | | 3-11 | 32-42-11 | D00321A | | D03 | | D41664J | 12 | | *L | 001-099 | | |
| 6241 | 24 | | GK | | 3-11 | 32-42-11 | D00321A | | D03 | | D41664J | 39 | | *L | 115-199 | | |
| 6242 | 24 | | GK | | 2-11 | 32-42-11 | D00319A | | D03 | | D41664J | 12 | | *L | 001-099 | | |
| 6242 | 24 | | GK | | 2-11 | 32-42-11 | D00319A | | D03 | | D41664J | 39 | | *L | 115-199 | | |
| 6243 | 24 | | GK | | 2-11 | 27-51-51 | D41698J | | 7 | *M | D00319D | B15 | | | 001-099 | | |
| 6243 | 24 | | GK | | 2-11 | 27-51-51 | D00319D | | B15 | | D41698J | 7 | | *M | 115-199 | | |
| 6244 | 24 | | GK | | 3-10 | 27-51-51 | D41698J | | 7 | *M | D00321D | B15 | | | 001-099 | | |
| 6244 | 24 | | GK | | 3-10 | 27-51-51 | D00321D | | B15 | | D41698J | 7 | | *M | 115-199 | | |
| 6245 | 24 | | GK | | 2-8 | 32-46-11 | D42073J | | 1 | | TB0207Y | A083 | BJ | | 115-199 | | |
| 6251 | 24 | | GK | | 3-9 | 21-61-51 | D00319D | | B08 | | D42084J | 41 | | *1 | 001-099 | | |
| 6251 | 24 | | GK | | 4-0 | 21-61-51 | D00319D | | B08 | | D42084J | 55 | | *1 | 115-199 | | |
| 6252 | 24 | | GK | | 5-2 | 21-61-51 | D00321D | | B08 | | D42084J | 41 | | *1 | 001-099 | | |
| 6252 | 24 | | GK | | 5-4 | 21-61-51 | D00321D | | B08 | | D42084J | 55 | | *1 | 115-199 | | |
| 6253 | 24 | | GK | | 3-3 | 29-21-31 | D00321F | | K06 | | D41736J | 45 | | *Q | ALL | | |
| 6254 | 24 | | GK | | 3-0 | 29-21-31 | D00319F | | K06 | | D41736J | 45 | | *Q | 001-099 | | |
| 6254 | 24 | | GK | | 2-11 | 29-21-31 | D00319F | | K06 | | D41736J | 45 | | *Q | 115-199 | | |
| 6255 | 24 | | GK | | 3-3 | 29-21-31 | D00321F | | H06 | | D41736J | 39 | | *Q | ALL | | |
| 6256 | 24 | | GK | | 3-0 | 29-21-31 | D00319F | | H06 | | D41736J | 39 | | *Q | 001-099 | | |
| 6256 | 24 | | GK | | 2-11 | 29-21-31 | D00319F | | H06 | | D41736J | 39 | | *Q | 115-199 | | |
| 6257 | 22 | | GA | | 2-10 | 31-41-11 | D00789 | | 57 | | GD02215 | DC.. | 2 | | ALL | | |
| 6258 | 22 | | GA | | 2-10 | 31-41-21 | D00791 | | 57 | | GD02215 | DC.. | 2 | | ALL | | |
| 6259 | 24 | | GK | | 3-7 | 24-51-72 | D00319B | | J14 | | D40904J | 12 | | *D | ALL | | |
| 6260 | 24 | | GK | | 3-0 | 24-51-72 | D00321B | | J14 | | D40904J | 12 | | *D | ALL | | |
| 6261 | 24 | | GK | | 3-1 | 24-51-72 | D00319B | | H14 | | TB0207Y | A094 | BJ | | 001, 003-099 | | |
| 6261 | 24 | | GK | | 3-2 | 24-51-72 | D00319B | | H14 | | TB0207Y | A094 | BJ | | 002 | | |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 151

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | |
| 6261 | 24 | GK | | | 3-3 | 24-51-72 | D00319B | H14 | | | TB0207Y | A094 | BJ | | 115-199 |
| 6262 | 24 | GK | | | 2-8 | 24-51-72 | D00321B | H14 | | | TB0207Y | A094 | BJ | | 001-099 |
| 6262 | 24 | GK | | | 2-9 | 24-51-72 | D00321B | H14 | | | TB0207Y | A094 | BJ | | 115-199 |
| 6263 | 24 | GK | | | 3-11 | 27-23-21 | D00321E | D08 | | | D41879J | 35 | | *Z | ALL |
| 6264 | 24 | GK | | | 4-0 | 27-23-21 | D00321B | E08 | | | D41879J | 36 | | *Z | ALL |
| 6265 | 24 | GK | | | 3-9 | 27-23-21 | D00321F | D07 | | | D41879J | 37 | | *Z | 001-099 |
| 6265 | 24 | GK | | | 3-10 | 27-23-21 | D00321F | D07 | | | D41879J | 37 | | *Z | 115-199 |
| 6266 | 24 | GK | | | 2-6 | 27-23-21 | D00319E | D08 | | | D41879J | 35 | | *Z | 001-099 |
| 6266 | 24 | GK | | | 2-7 | 27-23-21 | D00319E | D08 | | | D41879J | 35 | | *Z | 115-199 |
| 6267 | 24 | GK | | | 2-7 | 27-23-21 | D00319B | E08 | | | D41879J | 36 | | *Z | ALL |
| 6268 | 24 | GK | | | 2-5 | 27-23-21 | D00319F | D07 | | | D41879J | 37 | | *Z | 001-099 |
| 6268 | 24 | GK | | | 2-6 | 27-23-21 | D00319F | D07 | | | D41879J | 37 | | *Z | 115-199 |
| 6274 | 22 | GA | | | 5-5 | 29-11-12 | D41867J | 28 | | | D41738J | 24 | | | 001-099 |
| 6274 | 22 | GA | | | 6-1 | 29-11-12 | D41867J | 28 | | | D41738J | 24 | | | 115-199 |
| 6275 | 22 | GA | | | 3-3 | 29-11-22 | D41776J | 28 | | | D41879J | 38 | | | ALL |
| 6276 | 24 | GK | | | 2-9 | 28-41-13 | D00321E | D03 | | | D40584J | 37 | | *C | 001-099 |
| 6276 | 24 | GK | | | 2-10 | 28-41-13 | D00321E | D03 | | | D40584J | 37 | | *C | 115-199 |
| 6277 | 24 | GK | | | 3-11 | 28-41-13 | D00319E | D03 | | | D40584J | 37 | | *C | ALL |
| 6278 | 24 | GK | | | 3-3 | 30-31-12 | D00321E | K12 | | | D41720J | 3 | | *N | ALL |
| 6279 | 24 | GK | | | 3-0 | 30-31-12 | D00319E | K12 | | | D41720J | 3 | | *N | ALL |
| 6282 | 22 | GA | | | 1-0 | 79-34-11 | D41734J | | | RA | GD02211 | ST.. | 2 | | 001-099 |
| 6282 | 22 | GA | | | 2-7 | 79-34-11 | D41734J | | | RA | GD02209 | ST.. | 2 | | 115-199 |
| 6283 | 22 | GA | | | 1-0 | 79-34-11 | D41736J | | | RB | GD02211 | ST.. | 2 | | 001-099 |
| 6283 | 22 | GA | | | 2-10 | 79-34-11 | D41736J | | | RB | GD02209 | ST.. | 2 | | 115-199 |
| 6284 | 20 | GA | | | 1-9 | 49-71-11 | TB0207C | C122 | 2 | | GD02215 | DC.. | 2 | | 001-099 |
| 6284 | 20 | GA | | | 1-8 | 49-71-11 | TB0207C | C122 | 2 | | GD02215 | DC.. | 2 | | 115-199 |
| 6285 | 20 | GA | | | 1-9 | 49-73-11 | TB0207C | C121 | 2 | | GD02215 | DC.. | 2 | | 001-099 |
| 6285 | 20 | GA | | | 1-8 | 49-73-11 | TB0207C | C121 | 2 | | GD02215 | DC.. | 2 | | 115-199 |
| 6286 | 22 | GA | | | 4-0 | 77-31-11 | D04240B | A15 | | | GD02213 | DC.. | 2 | | 001-099 |
| 6286 | 22 | GA | | | 3-11 | 77-31-11 | D04240B | A15 | | | GD02213 | DC.. | 2 | | 115-199 |
| 6287 | 24 | GK | | | 4-10 | 75-31-11 | D00321D | J03 | | | D41788J | 3 | | *1 | 001-099 |
| 6295 | 24 | GK | | | 2-8 | 49-94-11 | D00319E | K04 | | | D41660J | 9 | | *K | 001-099 |
| 6296 | 24 | GK | | | 4-0 | 49-94-11 | D00321E | K04 | | | D41660J | 9 | | *K | 001-099 |
| 6299 | 24 | GK | | | 4-11 | 75-31-11 | D00321A | H05 | | | D41772J | 3 | VP | *T | 001-099 |
| 6300 | 24 | GK | | | 3-7 | 75-31-11 | D00319A | H05 | | | D41772J | 3 | VP | *T | 001-099 |
| 6301 | 24 | GK | | | 4-10 | 75-31-11 | D00321D | J02 | | | D41788J | 2 | VP | *1 | 001-099 |
| 6302 | 24 | GK | | | 3-6 | 75-31-11 | D00319D | J02 | | | D41788J | 2 | VP | *1 | 001-099 |
| 6305 | 22 | GA | | | 4-0 | 29-11-22 | D41840J | 4 | | | TB0207Z | 104 | BJ | | 115-199 |
| 6306 | 22 | GA | | | 4-8 | 29-11-12 | D41738J | 22 | | | TB0207Z | 28 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 152

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6308 | 22 | | GA | | 3-6 | 29-11-12 | D41632J | | 9 | | TB0207Y | C025 | BJ | | 115-199 |
| 6323 | 24 | | GK | | 2-10 | 73-21-11 | D00319B | | H08 | | D41734J | 42 | | *P | 001-099 |
| 6324 | 24 | | GK | | 3-3 | 73-21-11 | D00321B | | H08 | | D41734J | 42 | | *P | 001-099 |
| 6331 | 24 | | GK | | 3-3 | 73-21-21 | D00319D | | H04 | | D41736J | 36 | | *Q | 001-099 |
| 6332 | 24 | | GK | | 3-6 | 73-21-21 | D00321D | | H04 | | D41736J | 36 | | *Q | 001-099 |
| 6401 | 24 | | GK | | 3-11 | 21-52-21 | D00321E | | J12 | | D42086J | 15 | | | 001-099 |
| 6401 | 24 | | GK | | 4-6 | 21-52-21 | D00321E | | J12 | | D42086J | 15 | | | 115-199 |
| 6402 | 24 | | GK | | 2-11 | 21-52-21 | D42086J | | 16 | | TB0207Z | 77 | BJ | | 001-099 |
| 6402 | 24 | | GK | | 3-8 | 21-52-21 | TB0207Z | | 77 | BJ | D42086J | 16 | | | 115-199 |
| 6405 | 24 | | GK | | 4-1 | 21-52-21 | D42084J | | 16 | | TB0207Z | 77 | BJ | | 001-099 |
| 6405 | 24 | | GK | | 4-5 | 21-52-21 | TB0207Z | | 77 | BJ | D42084J | 16 | | | 115-199 |
| 6406 | 24 | | GK | | 3-8 | 21-52-21 | D00319E | | J12 | | D42084J | 15 | | | 001-099 |
| 6406 | 24 | | GK | | 3-11 | 21-52-21 | D00319E | | J12 | | D42084J | 15 | | | 115-199 |
| 6407 | 22 | | GA | | 4-7 | 29-11-12 | D41738J | | 22 | | TB0207Y | C026 | BJ | | 001, 003-099 |
| 6407 | 22 | | GA | | 4-8 | 29-11-12 | D41738J | | 22 | | TB0207Y | C026 | BJ | | 002 |
| 6408 | 22 | | GA | | 2-5 | 29-11-12 | D41738J | | 21 | | TB0207Z | 103 | BJ | | 001-099 |
| 6411 | 24 | | GK | | 3-4 | 27-09-14 | D41867J | | 41 | | TB0207Y | C039 | BJ | | 001, 003-099 |
| 6411 | 24 | | GK | | 3-5 | 27-09-14 | D41867J | | 41 | | TB0207Y | C039 | BJ | | 002, 115-199 |
| 6412 | 24 | | GK | | 4-0 | 27-09-14 | D00321A | | H14 | | TB0207Y | C039 | BJ | | 001, 003-099 |
| 6412 | 24 | | GK | | 4-1 | 27-09-14 | D00321A | | H14 | | TB0207Y | C039 | BJ | | 002, 115-199 |
| 6413 | 24 | | GK | | 2-7 | 27-09-14 | D42185J | | 25 | | TB0207Y | C039 | BJ | | 001, 003-099 |
| 6413 | 24 | | GK | | 2-8 | 27-09-14 | D42185J | | 25 | | TB0207Y | C039 | BJ | | 002 |
| 6413 | 24 | | GK | | 2-9 | 27-09-14 | D42185J | | 25 | | TB0207Y | C039 | BJ | | 115-199 |
| 6414 | 24 | | GK | | 2-7 | 27-09-14 | D00319A | | H14 | | TB0207Y | C039 | BJ | | 001, 003-099 |
| 6414 | 24 | | GK | | 2-8 | 27-09-14 | D00319A | | H14 | | TB0207Y | C039 | BJ | | 002, 115-199 |
| 6419 | 24 | | GK | | 3-4 | 27-09-14 | D41867J | | 43 | | TB0207Y | A043 | BJ | | 001, 003-099 |
| 6419 | 24 | | GK | | 3-5 | 27-09-14 | D41867J | | 43 | | TB0207Y | A043 | BJ | | 002, 115-199 |
| 6420 | 24 | | GK | | 3-10 | 27-09-14 | D00321E | | K13 | | TB0207Y | A043 | BJ | | 001, 003-099, 115-199 |
| 6420 | 24 | | GK | | 3-11 | 27-09-14 | D00321E | | K13 | | TB0207Y | A043 | BJ | | 002 |
| 6421 | 24 | | GK | | 2-7 | 27-09-14 | D42185J | | 29 | | TB0207Y | A043 | BJ | | 001, 003-099 |
| 6421 | 24 | | GK | | 2-8 | 27-09-14 | D42185J | | 29 | | TB0207Y | A043 | BJ | | 002 |
| 6421 | 24 | | GK | | 2-9 | 27-09-14 | D42185J | | 29 | | TB0207Y | A043 | BJ | | 115-199 |
| 6422 | 24 | | GK | | 2-5 | 27-09-14 | D00319E | | K13 | | TB0207Y | A043 | BJ | | 001, 003-099 |
| 6422 | 24 | | GK | | 2-6 | 27-09-14 | D00319E | | K13 | | TB0207Y | A043 | BJ | | 002, 115-199 |
| 6423 | 24 | | GK | | 3-8 | 27-09-14 | D41867J | | 44 | | TB0207Y | C058 | BJ | | 001-099 |
| 6423 | 24 | | GK | | 3-10 | 27-09-14 | D41867J | | 44 | | TB0207Y | C058 | BJ | | 115-199 |
| 6424 | 24 | | GK | | 3-6 | 27-09-14 | D00321E | | J11 | | TB0207Y | C058 | BJ | | 001-099 |
| 6424 | 24 | | GK | | 3-7 | 27-09-14 | D00321E | | J11 | | TB0207Y | C058 | BJ | | 115-199 |
| 6425 | 24 | | GK | | 2-3 | 27-09-14 | D42185J | | 30 | | TB0207Y | C058 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 153

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6425 | 24 | | GK | | 2-5 | 27-09-14 | D42185J | | 30 | | TB0207Y | C058 | BJ | | 115-199 |
| 6426 | 24 | | GK | | 2-4 | 27-09-14 | D00319E | | J11 | | TB0207Y | C058 | BJ | | 001-099 |
| 6426 | 24 | | GK | | 2-5 | 27-09-14 | D00319E | | J11 | | TB0207Y | C058 | BJ | | 115-199 |
| 6427 | 24 | | GK | | 3-9 | 27-09-14 | D41867J | | 45 | | TB0207Y | C067 | BJ | | 001, 003-099 |
| 6427 | 24 | | GK | | 3-10 | 27-09-14 | D41867J | | 45 | | TB0207Y | C067 | BJ | | 002 |
| 6427 | 24 | | GK | | 3-11 | 27-09-14 | D41867J | | 45 | | TB0207Y | C067 | BJ | | 115-199 |
| 6428 | 24 | | GK | | 3-4 | 27-09-14 | D00321E | | K09 | | TB0207Y | C067 | BJ | | 001, 003-099 |
| 6428 | 24 | | GK | | 3-5 | 27-09-14 | D00321E | | K09 | | TB0207Y | C067 | BJ | | 002, 115-199 |
| 6429 | 24 | | GK | | 2-1 | 27-09-14 | D42185J | | 31 | | TB0207Y | C067 | BJ | | 001, 003-099 |
| 6429 | 24 | | GK | | 2-2 | 27-09-14 | D42185J | | 31 | | TB0207Y | C067 | BJ | | 002 |
| 6429 | 24 | | GK | | 2-4 | 27-09-14 | D42185J | | 31 | | TB0207Y | C067 | BJ | | 115-199 |
| 6430 | 24 | | GK | | 2-5 | 27-09-14 | D00319E | | K09 | | TB0207Y | C067 | BJ | | 001, 003-099 |
| 6430 | 24 | | GK | | 2-6 | 27-09-14 | D00319E | | K09 | | TB0207Y | C067 | BJ | | 002, 115-199 |
| 6431 | 22 | | GA | | 4-0 | 29-11-22 | D41840J | | 4 | | TB0207Z | 104 | BJ | | 001-099 |
| 6432 | 24 | | GK | | 2-9 | 79-31-11 | D41736J | | 9 | | TB0207Y | A095 | BJ | | 001-099 |
| 6433 | 24 | | GK | | 2-4 | 79-31-11 | D41736J | | 10 | | TB0207Y | A079 | BJ | | 001, 003-099 |
| 6433 | 24 | | GK | | 2-5 | 79-31-11 | D41736J | | 10 | | TB0207Y | A079 | BJ | | 002 |
| 6434 | 24 | | GK | | 3-9 | 79-31-11 | D41736J | | 8 | | GD02205 | DC.. | 2 | | 001-099 |
| 6435 | 24 | | GK | | 2-2 | 79-31-11 | D41734J | | 9 | | TB0207Z | 78 | BJ | | 001-099 |
| 6436 | 24 | | GK | | 2-1 | 79-31-11 | D41734J | | 10 | | TB0207Y | C079 | BJ | | 001, 003-099 |
| 6436 | 24 | | GK | | 2-2 | 79-31-11 | D41734J | | 10 | | TB0207Y | C079 | BJ | | 002 |
| 6437 | 24 | | GK | | 3-11 | 79-31-11 | D41734J | | 8 | | GD02202 | DC.. | 2 | | 001-099 |
| 6438 | 24 | | GK | | 2-5 | 79-32-11 | D41736J | | 12 | | TB0207Y | C083 | BJ | | 001-099 |
| 6439 | 24 | | GK | | 3-9 | 79-32-11 | D41736J | | 11 | | GD02205 | AC.. | 2 | | 001-099 |
| 6440 | 24 | | GK | | 4-3 | 79-32-11 | D41736J | | 13 | | TB0207Y | A001 | BJ | | 001, 003-099 |
| 6440 | 24 | | GK | | 4-2 | 79-32-11 | D41736J | | 13 | | TB0207Y | A001 | BJ | | 002 |
| 6441 | 24 | | GK | | 2-2 | 79-32-11 | D41734J | | 12 | | TB0207Y | C084 | BJ | | 001-099 |
| 6442 | 24 | | GK | | 3-11 | 79-32-11 | D41734J | | 11 | | GD02202 | AC.. | 2 | | 001-099 |
| 6443 | 24 | | GK | | 4-0 | 79-32-11 | D41734J | | 13 | | TB0207Y | A002 | BJ | | 001, 003-099 |
| 6443 | 24 | | GK | | 3-11 | 79-32-11 | D41734J | | 13 | | TB0207Y | A002 | BJ | | 002 |
| 6444 | 24 | | GK | | 3-7 | 31-51-43 | D00319B | | C14 | | D41451J | 36 | | *H | ALL |
| 6445 | 24 | | GK | | 3-0 | 31-51-43 | D00321B | | C14 | | D41451J | 36 | | *H | ALL |
| 6477 | 24 | | GK | | 4-3 | 30-34-21 | D00321D | | B11 | | D41840J | 9 | | *W | ALL |
| 6479 | 24 | | GK | | 2-11 | 30-34-21 | D00319D | | B11 | | D41840J | 9 | | *W | 001-099 |
| 6479 | 24 | | GK | | 3-0 | 30-34-21 | D00319D | | B11 | | D41840J | 9 | | *W | 115-199 |
| 6480 | 24 | | GK | | 4-0 | 30-34-22 | D00321E | | A08 | | D41058J | 30 | | *E | 001-099 |
| 6480 | 24 | | GK | | 4-1 | 30-34-22 | D00321E | | A08 | | D41058J | 30 | | *E | 115-199 |
| 6481 | 24 | | GK | | 2-8 | 30-34-22 | D00319E | | A08 | | D41058J | 30 | | *E | 001-099 |
| 6481 | 24 | | GK | | 2-9 | 30-34-22 | D00319E | | A08 | | D41058J | 30 | | *E | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 154

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6489 | 22 | | GA | | 3-4 | 32-44-11 | D41734J | 51 | | | TB0207Y | C027 | BJ | | 001, 003-099 |
| 6489 | 22 | | GA | | 3-5 | 32-44-11 | D41734J | 51 | | | TB0207Y | C027 | BJ | | 002 |
| 6494 | 24 | | GK | | 4-7 | SPARE | D41867J | 51 | | | TB0207Y | C100 | BJ | | 115-199 |
| 6495 | 24 | | GK | | 3-1 | SPARE | D41879J | 54 | | | TB0207Y | C083 | BJ | | 115-199 |
| 6496 | 24 | | GK | | 5-0 | 31-51-33 | D41867J | 50 | | | TB0207Z | 108 | BJ | | 115-199 |
| 6497 | 24 | | GK | | 4-4 | 31-51-33 | D41369J | 22 | | | TB0207Z | 73 | BJ | | 115-199 |
| 6498 | 24 | | GK | | 3-1 | 31-51-33 | D41879J | 53 | | | TB0207Z | 73 | BJ | | 115-199 |
| 6499 | 24 | | GK | | 4-0 | 31-51-33 | D41317J | 23 | | | TB0207Z | 108 | BJ | | 115-199 |
| 6501 | 24 | | GK | | 2-5 | 24-51-72 | D40904J | 11 | | | TB0207Y | A094 | BJ | | ALL |
| 6504 | 24 | | GK | | 2-9 | 77-31-11 | D41772J | 30 | | | GD02204 | DC.. | 2 | | 001-099 |
| 6505 | 24 | | GK | | 2-8 | 77-31-11 | D04240B | C07 | | | D41772J | 31 | | *T | 001-008 |
| 6505 | 24 | | GK | | 2-8 | 77-31-11 | D04240B | CAP | Y | | D41772J | 31 | | *T | 009-099 |
| 6506 | 24 | | GK | | 2-11 | 77-31-11 | D05602B | C07 | | | D41772J | 31 | | *T | 001-008 |
| 6506 | 24 | | GK | | 2-11 | 77-31-11 | D05602B | CAP | Y | | D41772J | 31 | | *T | 009-099 |
| 6507 | 24 | | GK | | 3-11 | 49-73-11 | D41660J | 19 | | | TB0207C | A121 | 2 | | 001-099 |
| 6508 | 24 | | GK | | 3-11 | 49-71-11 | D41660J | 17 | | | TB0207C | A122 | 2 | | 001-099 |
| 6509 | 24 | | GK | | 4-0 | 24-25-13 | D00321F | J04 | | | D41317J | 55 | | *F | 001-099 |
| 6509 | 24 | | GK | | 4-1 | 24-25-13 | D00321F | CAP | Y | | D41317J | 55 | | *F | 115-199 |
| 6510 | 24 | | GK | | 4-2 | 24-25-13 | D00321E | B13 | | | D41317J | 44 | | *F | 001-099 |
| 6510 | 24 | | GK | | 4-2 | 24-25-13 | D00321E | CAP | Y | | D41317J | 44 | | *F | 115-199 |
| 6511 | 24 | | GK | | 2-8 | 24-25-13 | D00319F | J04 | | | D41317J | 55 | | *F | 001-099 |
| 6511 | 24 | | GK | | 2-9 | 24-25-13 | D00319F | CAP | Y | | D41317J | 55 | | *F | 115-199 |
| 6512 | 24 | | GK | | 2-9 | 24-25-13 | D00319E | B13 | | | D41317J | 44 | | *F | 001-099 |
| 6512 | 24 | | GK | | 2-10 | 24-25-13 | D00319E | CAP | Y | | D41317J | 44 | | *F | 115-199 |
| 6520 | 24 | | GK | | 3-0 | 24-11-11 | D00319F | G01 | | | TB0207Y | A099 | BJ | | ALL |
| 6521 | 24 | | GK | | 3-0 | 24-11-11 | D00321F | G01 | | | TB0207Y | A099 | BJ | | ALL |
| 6522 | 24 | | GK | | 3-0 | 24-11-11 | D40584J | 23 | | | TB0207Y | A099 | BJ | | ALL |
| 6526 | 24 | | GK | | 4-0 | 24-11-21 | D41058J | 41 | | | TB0207Y | A098 | BJ | | ALL |
| 6527 | 24 | | GK | | 3-0 | 24-11-21 | D00321F | G03 | | | TB0207Y | A098 | BJ | | ALL |
| 6528 | 24 | | GK | | 3-0 | 24-11-21 | D00319F | G03 | | | TB0207Y | A098 | BJ | | ALL |
| 6603 | 24 | | GK | | 3-4 | 34-53-11 | D41317J | 16 | | | TB0207A | C081 | 2 | | 115-199 |
| 6604 | 24 | | GK | | 4-4 | 34-53-11 | D41369J | 30 | | | TB0207A | C082 | 2 | | 115-199 |
| 6605 | 24 | | GK | | 0-7 | 34-53-11 | TB0207A | C081 | 2 | | TB0207A | C082 | 2 | | 115-199 |
| 6607 | 24 | | GK | | 2-4 | 34-53-11 | D41451J | 10 | | | TB0207Y | C089 | BJ | | 001, 003-099 |
| 6607 | 24 | | GK | | 2-5 | 34-53-11 | D41451J | 10 | | | TB0207Y | C089 | BJ | | 002 |
| 6609 | 22 | | PA | | 6-0 | 34-61-26 | D41867J | 31 | | | TB0207Y | A119 | BJ | | 115-199 |
| 6625 | 22 | | PA | | 5-0 | 34-22-37 | D42023J | 19 | | | TB0207Y | A119 | BJ | | 115-199 |
| 6685 | 22 | | GA | | 3-0 | 31-51-41 | TB0207Y | A040 | BJ | | D41317J | 7 | | | 002 |
| 6686 | 22 | | GA | | 4-0 | 31-51-41 | D41867J | 18 | | | TB0207Y | C049 | BJ | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 155

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| 6723 | 22 | | GA | | 3-0 | 34-43-14 | | D41879J | 50 | | | TB0207Y | A040 | BJ | | 002 |
| 6724 | 22 | | GA | | 4-5 | 34-43-14 | | D41867J | 2 | | | TB0207Y | C049 | BJ | | 002 |
| 6725 | 22 | | GA | | 4-0 | 34-43-14 | | D41867J | 16 | | | TB0207Y | A050 | BJ | | 002 |
| 6726 | 22 | | GA | | 4-0 | 34-43-14 | | TB0207Y | A050 | BJ | | D00321B | G07 | | | 002 |
| 6727 | 22 | | GA | | 3-0 | 34-43-14 | | TB0207Y | A050 | BJ | | D00319B | G07 | | | 002 |
| 8275 | 24 | | GK | | 4-0 | 34-46-12 | | D00321B | G13 | | | D41451J | 53 | | *H | 002 |
| 8342 | 24 | | GK | | 3-0 | 34-46-12 | | D00319B | G13 | | | D41451J | 53 | | *H | 002 |
| A-BL | | | | | 0-0 | 77-12-11 | | TB0207E | 113 | | | TB0207Y | A109 | BJ | | ALL |
| A-GR | | | | | 0-0 | 77-12-11 | | TB0207E | 113 | | | TB0207Y | C109 | BJ | | ALL |
| A-RD | | | | | 0-0 | 77-12-11 | | TB0207E | 113 | | | TB0207Z | 107 | BJ | | ALL |
| A-WT | | | | | 0-0 | 77-12-11 | | TB0207E | 113 | | | GD02213 | DC.. | 2 | | 001-099 |
| A-WT | | | | | 0-0 | 77-12-11 | | TB0207E | 113 | | | GD02215 | DC.. | 2 | | 115-199 |
| A-YL | | | | | 0-0 | 77-12-11 | | TB0207E | 113 | | | TB0207Z | 106 | BJ | | ALL |
| B-BL | | | | | 0-0 | 77-12-11 | | TB0207E | 114 | | | TB0207Y | A110 | BJ | | ALL |
| B-GR | | | | | 0-0 | 77-12-11 | | TB0207E | 114 | | | TB0207Y | C110 | BJ | | ALL |
| B-RD | | | | | 0-0 | 77-12-11 | | TB0207E | 114 | | | TB0207Z | 112 | BJ | | ALL |
| B-WT | | | | | 0-0 | 77-12-11 | | TB0207E | 114 | | | GD02215 | DC.. | 2 | | ALL |
| B-YL | | | | | 0-0 | 77-12-11 | | TB0207E | 114 | | | TB0207Z | 111 | BJ | | ALL |
| C-BL | | | | | 0-0 | 77-11-11 | | TB0207D | 5 | | | TB0207Y | A003 | BJ | | ALL |
| C-RD | | | | | 0-0 | 77-11-11 | | TB0207D | 5 | | | TB0207Y | A086 | BJ | | ALL |
| C-YL | | | | | 0-0 | 77-11-11 | | TB0207D | 5 | | | GD02205 | ST.. | 2 | | 001-099 |
| C-YL | | | | | 0-0 | 77-11-11 | | TB0207D | 5 | | | GD02202 | ST.. | 2 | | 115-199 |
| D-BL | | | | | 0-0 | 77-11-11 | | TB0207D | 6 | | | TB0207Y | C003 | BJ | | ALL |
| D-RD | | | | | 0-0 | 77-11-11 | | TB0207D | 6 | | | TB0207Y | C086 | BJ | | ALL |
| D-YL | | | | | 0-0 | 77-11-11 | | TB0207D | 6 | | | GD02202 | ST.. | 2 | | ALL |
| E-BL | | | | | 0-0 | 77-11-11 | | TB0207D | 101 | | | TB0207Y | A004 | BJ | | ALL |
| E-RD | | | | | 0-0 | 77-11-11 | | TB0207D | 101 | | | TB0207Z | 117 | BJ | | ALL |
| E-YL | | | | | 0-0 | 77-11-11 | | TB0207D | 101 | | | GD02215 | ST.. | 2 | | ALL |
| F-BL | | | | | 0-0 | 77-11-11 | | TB0207D | 102 | | | TB0207Y | C004 | BJ | | ALL |
| F-RD | | | | | 0-0 | 77-11-11 | | TB0207D | 102 | | | TB0207Z | 118 | BJ | | ALL |
| F-YL | | | | | 0-0 | 77-11-11 | | TB0207D | 102 | | | GD02215 | ST.. | 2 | | ALL |
| FRAA | | | | | 0-0 | 79-34-11 | | D41736J | 16 | | | D41736J | | | AA | ALL |
| FRAG | | | | | 0-0 | 79-34-11 | | D41734J | 16 | | | D41734J | | | AG | ALL |
| FRCA | | | | | 0-0 | 31-31-22 | | D41451J | 9 | | | D41451J | | | CA | 001-099 |
| FRCA | | | | | 0-0 | 31-31-21 | | D41451J | 9 | | | D41451J | | | CA | 115-199 |
| FRCK | | | | | 0-0 | 22-32-12 | | D41317J | 29 | | | D41317J | | | CK | ALL |
| FRCL | | | | | 0-0 | 22-32-12 | | D41369J | 36 | | | D41369J | | | CL | ALL |
| FRDQ | | | | | 0-0 | 31-41-19 | | D41065J | 12 | | | D41065J | | | DQ | ALL |
| FRDR | | | | | 0-0 | 31-41-19 | | D41065J | 7 | | | D41065J | | | DR | ALL |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 156

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1275 | 286N1275 | | | E4-2 SHELF -(N2) (continued) | | | | | | | | | | | |
| FRDS | | | | | 0-0 | 31-41-12 | D41317J | | 3 | | D41317J | | | DS | ALL |
| FRDT | | | | | 0-0 | 31-41-12 | D41317J | | 6 | | D41317J | | | DT | ALL |
| FREK | | | | | 0-0 | 31-41-22 | D41369J | | 6 | | D41369J | | | EK | ALL |
| FREL | | | | | 0-0 | 31-41-22 | D41369J | | 1 | | D41369J | | | EL | ALL |
| FREV | | | | | 0-0 | 34-61-15 | D41317J | | 18 | | D41317J | | | EV | ALL |
| FRFT | | | | | 0-0 | 77-31-11 | D41788J | | 14 | | D41788J | | | FT | ALL |
| FRFU | | | | | 0-0 | 77-31-11 | D41788J | | 16 | | D41788J | | | FU | ALL |
| FRFW | | | | | 0-0 | 77-31-11 | D41772J | | 16 | | D41772J | | | FW | ALL |
| FRFY | | | | | 0-0 | 77-31-11 | D41772J | | 14 | | D41772J | | | FY | ALL |
| FRHS | | | | | 0-0 | 34-61-14 | D41317J | | 12 | | D41317J | | | HS | ALL |
| FRJA | | | | | 0-0 | 34-61-24 | D41369J | | 9 | | D41369J | | | JA | ALL |
| FRJB | | | | | 0-0 | 34-61-25 | D41369J | | 16 | | D41369J | | | JB | ALL |
| FRJC | | | | | 0-0 | 34-25-11 | D41879J | | 6 | | D41879J | | | JC | 115-199 |
| FRJD | | | | | 0-0 | 34-25-11 | D41867J | | 15 | | D41867J | | | JD | 115-199 |
| FRKA | | | | | 0-0 | 73-21-22 | D42185J | | 21 | | D42185J | | | KA | 115-199 |
| FRKB | | | | | 0-0 | 73-21-22 | D41776J | | 17 | | D41776J | | | KB | 115-199 |
| FRRRA | | | | | 0-0 | 79-34-11 | D41734J | | | RA | D41734J | 43 | | | ALL |
| FRRB | | | | | 0-0 | 79-34-11 | D41736J | | | RB | D41736J | 44 | | | ALL |
| FRRS | | | | | 0-0 | 73-21-22 | D41776J | | 17 | | D41776J | | | RS | 001-099 |
| FRRT | | | | | 0-0 | 73-21-22 | D42185J | | 21 | | D42185J | | | RT | 001-099 |
| FRTD | | | | | 0-0 | 77-31-11 | TB0207Y | | | TD | GD02211 | ST.. | 2 | | 001-099 |
| FRTF | | | | | 0-0 | 77-12-21 | TB0207Y | | | TF | GD02202 | ST.. | 2 | | ALL |
| FRTG | | | | | 0-0 | 77-12-21 | TB0207Y | | | TG | GD02201 | ST.. | 2 | | ALL |
| FRTI | | | | | 0-0 | 77-31-11 | TB0207Y | | | TI | GD02204 | ST.. | 2 | | 001-099 |
| FRTM | | | | | 0-0 | 22-41-13 | TB0207Y | | | TM | GD02213 | ST.. | 2 | | 001-099 |
| FRUA | | | | | 0-0 | 28-41-11 | TB0207Y | | | UA | GD02210 | ST.. | 2 | | 001-099 |
| FRUA | | | | | 0-0 | 28-41-11 | TB0207Y | | | UA | GD02209 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1270

Page 157 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS | | | | | | | | | | | |
| 0001 | 24 | | GK | | 4-0 | 33-42-11 | D03210E | K08 | | | D42060J | 10 | | | 001-099 |
| 0001 | 22 | | GA | | 3-0 | 33-42-11 | D03210E | K08 | | | D42060J | 10 | | | 115-199 |
| 0002 | 22 | | GA | | 3-0 | 27-23-11 | D42060J | 8 | | | D41876J | 28 | | | 115-199 |
| 0003 | 22 | | GA | | 4-0 | 32-61-11 | D03210A | D07 | | | D41445J | 28 | | | 001-002 |
| 0003 | 22 | | GA | | 2-0 | 32-61-11 | SM00004 | | WI | | D41445J | 28 | | | 003-099 |
| 0003 | 22 | | GA | | 3-0 | 32-61-11 | D03210A | D07 | | | D41445J | 28 | | | 115-199 |
| 0004 | 22 | | GA | | 3-0 | 52-34-11 | D03210D | C03 | | | D41928J | 1 | | | ALL |
| 0005 | 22 | | GA | | 3-0 | 52-34-11 | D03210D | B03 | | | D41928J | 2 | | | ALL |
| 0006 | 22 | | GA | | 3-0 | 52-34-11 | D03210D | J03 | | | D41928J | 3 | | | ALL |
| 0007 | 22 | | GA | | 3-0 | 27-23-11 | D42060J | 9 | | | TB0182Y | A007 | BJ | | 115-199 |
| 0008 | 22 | | GA | | 4-0 | 27-23-11 | TB0182Y | A007 | BJ | | D41876J | 27 | | | 115-199 |
| 0009 | 22 | | GA | | 3-0 | 52-35-11 | D03210D | B07 | | | D41930J | 1 | | | ALL |
| 0010 | 22 | | GA | | 3-0 | 52-35-11 | D03210D | C07 | | | D41930J | 2 | | | ALL |
| 0011 | 24 | | GK | | 4-0 | 52-71-11 | D03210B | F06 | | | D40924J | 1 | | | 001-099 |
| 0011 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | F06 | | | D40924J | 1 | | | 115-199 |
| 0012 | 24 | | GK | | 4-0 | 52-71-11 | D03210B | G06 | | | D40924J | 2 | | | 001-099 |
| 0012 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | G06 | | | D40924J | 2 | | | 115-199 |
| 0013 | 24 | | GK | | 4-0 | 52-71-11 | D03210B | H06 | | | D40924J | 3 | | | 001-099 |
| 0013 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | H06 | | | D40924J | 3 | | | 115-199 |
| 0014 | 24 | | GK | | 4-0 | 52-71-11 | D03210B | J06 | | | D40924J | 4 | | | 001-099 |
| 0014 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | J06 | | | D40924J | 4 | | | 115-199 |
| 0015 | 22 | | GA | | 4-0 | 52-71-11 | D03210B | K08 | | | GD01882 | DC.. | 2 | | 001-099 |
| 0015 | 22 | | GA | | 3-0 | 52-71-11 | D03210B | K08 | | | GD01882 | DC.. | 2 | | 115-199 |
| 0016 | 22 | | GA | | 3-0 | 27-23-11 | D42060J | 12 | | | TB0182Y | A007 | BJ | | 115-199 |
| 0017 | 22 | | GA | | 3-0 | 27-23-11 | D42060J | 11 | | | TB0182Y | C007 | BJ | | 115-199 |
| 0018 | 22 | | GA | | 4-0 | 27-23-11 | D41876J | 29 | | | TB0182Y | C007 | BJ | | 115-199 |
| 0019 | 22 | | GA | | 3-0 | 27-23-11 | D42060J | 13 | | | TB0182Y | C007 | BJ | | 115-199 |
| 0023 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | J05 | | | D41618J | 5 | | | 001-099 |
| 0023 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | J05 | | | D41618J | 28 | | | 115-199 |
| 0024 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | K05 | | | D41618J | 4 | | | 001-099 |
| 0024 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | K05 | | | D41618J | 27 | | | 115-199 |
| 0025 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | A06 | | | D41618J | 3 | | | 001-099 |
| 0025 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | A06 | | | D41618J | 26 | | | 115-199 |
| 0026 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | B06 | | | D41618J | 2 | | | 001-099 |
| 0026 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | B06 | | | D41618J | 25 | | | 115-199 |
| 0027 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | B05 | | | D41618J | 24 | | | ALL |
| 0028 | 24 | | GK | | 3-0 | 52-71-11 | D03210B | C05 | | | D41618J | 22 | | | ALL |
| 0029 | 22 | | GA | | 5-0 | 52-71-11 | D03210B | J08 | | | D40702J | 15 | | | 001-099 |
| 0029 | 22 | | GA | | 4-0 | 52-71-11 | D03210B | J08 | | | D40702J | 15 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0030 | 22 | | GA | | 3-0 | 32-61-12 | | D41311J | | 11 | | TB0182Y | A008 | BJ | | 001-099 |
| 0030 | 22 | | GA | | 3-0 | 32-61-11 | | D41311J | | 32 | | TB0182Y | A008 | BJ | | 115-199 |
| 0031 | 22 | | GA | | 3-0 | 32-61-12 | | D42060J | | 3 | | TB0182Y | C013 | BJ | | ALL |
| 0032 | 24 | | GK | | 4-0 | 32-61-12 | | D41363J | | 26 | | TB0182Y | C009 | BJ | | 001-099 |
| 0032 | 24 | | GK | | 3-0 | 32-61-12 | | D41363J | | 26 | | TB0182Y | C009 | BJ | | 115-199 |
| 0033 | 22 | | GA | | 3-0 | 32-61-12 | | D42060J | | 5 | | TB0182Y | C012 | BJ | | ALL |
| 0035 | 22 | | GA | | 3-0 | 32-61-12 | | D42060J | | 7 | | TB0182Y | A013 | BJ | | ALL |
| 0036 | 22 | | GA | | 4-0 | 32-61-12 | | D41363J | | 30 | | TB0182Y | C012 | BJ | | 001-099 |
| 0036 | 22 | | GA | | 3-0 | 32-61-12 | | D41363J | | 30 | | TB0182Y | C012 | BJ | | 115-199 |
| 0038 | 22 | | GA | | 4-0 | 32-61-12 | | D41363J | | 29 | | TB0182Y | A013 | BJ | | 001-099 |
| 0038 | 22 | | GA | | 3-0 | 32-61-12 | | D41363J | | 29 | | TB0182Y | A013 | BJ | | 115-199 |
| 0039 | 22 | | GA | | 3-0 | 32-61-12 | | D03210A | | F08 | | TB0182Y | C012 | BJ | | ALL |
| 0041 | 22 | | GA | | 3-0 | 32-61-12 | | D03210E | | C06 | | TB0182Y | A013 | BJ | | ALL |
| 0042 | 24 | | GK | | 4-0 | 52-71-21 | | D03210B | | E05 | | D41445J | 2 | | | 001-099 |
| 0042 | 24 | | GK | | 3-0 | 52-71-21 | | D03210B | | E05 | | D41445J | 2 | | | 115-199 |
| 0043 | 24 | | GK | | 4-0 | 52-71-21 | | D03210B | | F05 | | D41445J | 6 | | | 001-099 |
| 0043 | 24 | | GK | | 3-0 | 52-71-21 | | D03210B | | F05 | | D41445J | 6 | | | 115-199 |
| 0044 | 24 | | GK | | 4-0 | 52-71-21 | | D03210B | | G05 | | D41445J | 7 | | | 001-099 |
| 0044 | 24 | | GK | | 3-0 | 52-71-21 | | D03210B | | G05 | | D41445J | 7 | | | 115-199 |
| 0045 | 24 | | GK | | 4-0 | 52-71-21 | | D03210B | | H05 | | D41445J | 3 | | | 001-099 |
| 0045 | 24 | | GK | | 3-0 | 52-71-21 | | D03210B | | H05 | | D41445J | 3 | | | 115-199 |
| 0046 | 24 | | GK | | 4-0 | 52-71-21 | | D03210B | | A05 | | D41445J | 4 | | | 001-099 |
| 0046 | 24 | | GK | | 3-0 | 52-71-21 | | D03210B | | A05 | | D41445J | 4 | | | 115-199 |
| 0047 | 24 | | GK | | 4-0 | 52-71-21 | | D03210B | | D05 | | D41445J | 5 | | | 001-099 |
| 0047 | 24 | | GK | | 3-0 | 52-71-21 | | D03210B | | D05 | | D41445J | 5 | | | 115-199 |
| 0048 | 24 | | GK | | 4-0 | 78-36-11 | | D03210E | | A12 | | D42016J | 11 | | | 001-099 |
| 0048 | 24 | | GK | | 3-0 | 78-36-11 | | D03210E | | A12 | | D42016J | 11 | | | 115-199 |
| 0049 | 24 | | GK | | 4-0 | 78-36-11 | | D03210E | | E12 | | D42016J | 12 | | | ALL |
| 0050 | 24 | | GK | | 3-0 | 32-61-12 | | D03210E | | A07 | | D41363J | 27 | | | 001-099 |
| 0050 | 24 | | GK | | 2-0 | 32-61-12 | | D03210E | | A07 | | D41363J | 27 | | | 115-199 |
| 0051 | 22 | | GA | | 4-0 | 32-61-12 | | D41363J | | 25 | | TB0182Y | C013 | BJ | | 001-099 |
| 0051 | 22 | | GA | | 3-0 | 32-61-12 | | D41363J | | 25 | | TB0182Y | C013 | BJ | | 115-199 |
| 0052 | 24 | | GK | | 4-0 | 78-36-21 | | D03210A | | A12 | | D42018J | 9 | | | 001-099 |
| 0052 | 24 | | GK | | 3-0 | 78-36-21 | | D03210A | | A12 | | D42018J | 9 | | | 115-199 |
| 0053 | 24 | | GK | | 4-0 | 78-36-21 | | D03210A | | E12 | | D42018J | 10 | | | 001-099 |
| 0053 | 24 | | GK | | 3-0 | 78-36-21 | | D03210A | | E12 | | D42018J | 10 | | | 115-199 |
| 0054 | 24 | | GK | | 4-0 | 78-36-21 | | D03210A | | J14 | | D42018J | 16 | | | 001-099 |
| 0054 | 24 | | GK | | 3-0 | 78-36-21 | | D03210A | | J14 | | D42018J | 16 | | | 115-199 |
| 0055 | 24 | | GK | | 3-0 | 78-36-21 | | D03210A | | K14 | | GD01883 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------------------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | |
| 0055 | 22 | GA | | | 3-0 | 78-36-21 | D03210A | K14 | | | GD01883 | DC.. | 2 | | 115-199 |
| 0056 | 24 | GK | | | 4-0 | 78-36-11 | D03210E | J14 | | | D42016J | 15 | | | ALL |
| 0057 | 24 | GK | | | 3-0 | 78-36-11 | D03210E | K14 | | | GD01883 | DC.. | 2 | | 001-099 |
| 0057 | 22 | GA | | | 3-0 | 78-36-11 | D03210E | K14 | | | GD01883 | DC.. | 2 | | 115-199 |
| 0058 | 20 | GA | | | 4-0 | 32-35-11 | D42018J | 17 | | | TB0182Z | 15 | BJ | | 001-099 |
| 0058 | 20 | GA | | | 3-0 | 32-35-11 | D42018J | 17 | | | TB0182Z | 15 | BJ | | 115-199 |
| 0059 | 20 | GA | | | 4-0 | 32-35-11 | D42012J | 16 | | | TB0182Z | 15 | BJ | | 001-099 |
| 0059 | 20 | GA | | | 3-0 | 32-35-11 | D42012J | 16 | | | TB0182Z | 15 | BJ | | 115-199 |
| 0062 | 22 | GA | | | 4-0 | 32-42-11 | D42012J | 18 | | | D42014J | 13 | | | ALL |
| 0063 | 20 | GA | | | 4-0 | 32-12-12 | D42018J | 18 | | | TB0182Z | 15 | BJ | | 001-099 |
| 0063 | 20 | GA | | | 3-0 | 32-12-12 | D42018J | 18 | | | TB0182Z | 15 | BJ | | 115-199 |
| 0064 | 20 | GA | | | 4-0 | 32-12-12 | D41650J | 6 | | | TB0182Y | A009 | BJ | | 001-099 |
| 0064 | 20 | GA | | | 3-0 | 32-12-12 | D41650J | 6 | | | TB0182Y | A009 | BJ | | 115-199 |
| 0065 | 20 | GA | | | 4-0 | 32-12-12 | D41650J | 5 | | | TB0182Y | C008 | BJ | | 001-099 |
| 0065 | 20 | GA | | | 3-0 | 32-12-12 | D41650J | 5 | | | TB0182Y | C008 | BJ | | 115-199 |
| 0066 | 20 | GA | | | 3-0 | 32-12-12 | D41634J | 4 | | | TB0182Y | A009 | BJ | | 001-099 |
| 0066 | 20 | GA | | | 4-0 | 32-12-12 | D41634J | 4 | | | TB0182Y | A009 | BJ | | 115-199 |
| 0067 | 20 | GA | | | 3-0 | 32-12-12 | D41634J | 5 | | | TB0182Y | C008 | BJ | | 001-099 |
| 0067 | 20 | GA | | | 4-0 | 32-12-12 | D41634J | 5 | | | TB0182Y | C008 | BJ | | 115-199 |
| 0068 | 20 | GA | | | 4-0 | 32-12-12 | D40680J | 6 | | | TB0182Y | C008 | BJ | | ALL |
| 0069 | 20 | GA | | | 4-0 | 32-35-11 | D42169J | 5 | | | TB0182Z | 15 | BJ | | ALL |
| 0070 | 20 | GA | | | 4-0 | 32-35-11 | D42169J | 7 | | | D42016J | 17 | | | 001-099 |
| 0070 | 20 | GA | | | 5-0 | 32-35-11 | D42169J | 7 | | | D42016J | 17 | | | 115-199 |
| 0071 | 20 | GA | | | 4-0 | 32-35-11 | D42169J | 6 | | | D42018J | 19 | | | 001-099 |
| 0071 | 20 | GA | | | 5-0 | 32-35-11 | D42169J | 6 | | | D42018J | 19 | | | 115-199 |
| 0073 | 24 | GK | | | 3-0 | 32-61-12 | D03210A | K06 | | | TB0182C | C027 | 2 | | 001-099 |
| 0073 | 24 | GK | | | 3-0 | 32-61-11 | D03210A | K06 | | | TB0182C | C027 | 2 | | 115-199 |
| 0074 | 24 | GK | | | 2-0 | 32-61-12 | D41311J | 31 | | | SM00003 | | WI | | 001, 003-099 |
| 0074 | 24 | GK | | | 2-0 | 32-61-12 | D41311J | 31 | | | SM00003 | | W | | 002 |
| 0074 | 24 | GK | | | 4-0 | 32-61-11 | D41311J | 31 | | | SM00003 | | WI | | 115-199 |
| 0075 | 22 | GA | | | 3-0 | 32-61-12 | D42060J | 4 | | | TB0182Y | A008 | BJ | | ALL |
| 0076 | 24 | GK | | | 4-0 | 31-51-33 | D42014J | 1 | | | D41363J | 3 | | | ALL |
| 0077 | 24 | GK | | | 4-0 | 31-51-33 | D42012J | 6 | | | D41311J | 9 | | | ALL |
| 0078 | 24 | GK | | | 2-0 | 31-51-33 | D42016J | 14 | | | D41445J | 15 | | | 001-099 |
| 0078 | 24 | GK | | | 4-0 | 31-51-33 | D42016J | 14 | | | D41445J | 15 | | | 115-199 |
| 0079 | 24 | GK | | | 4-0 | 31-51-33 | D42012J | 10 | | | D41311J | 26 | | | ALL |
| 0080 | 24 | GK | | | 4-0 | 31-51-33 | D42014J | 8 | | | D41363J | 20 | | | ALL |
| 0081 | 24 | GK | | | 4-0 | 31-51-41 | D42018J | 13 | | | D41363J | 4 | | | ALL |
| 0082 | 24 | GK | | | 3-0 | 32-61-12 | D03210A | A07 | | | D41311J | 17 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0082 | 24 | | GK | | 3-0 | 32-61-11 | D03210A | A07 | | | D41311J | 17 | | | 115-199 |
| 0083 | 22 | | GA | | 3-0 | 32-61-12 | D41311J | 16 | | | TB0182Y | A009 | BJ | | 001-099 |
| 0083 | 22 | | GA | | 3-0 | 32-61-12 | D41311J | 36 | | | TB0182Y | A009 | BJ | | 115-199 |
| 0084 | 22 | | GA | | 3-0 | 32-61-12 | D03210E | J05 | | | TB0182Y | C013 | BJ | | ALL |
| 0085 | 22 | | GA | | 3-0 | 32-61-12 | D03210E | G03 | | | TB0182Y | A018 | BJ | | ALL |
| 0086 | 24 | | GK | | 3-0 | 32-61-12 | D03210A | H02 | | | D41311J | 3 | | | 001-099 |
| 0086 | 24 | | GK | | 3-0 | 32-61-12 | D03210A | H02 | | | D41311J | 37 | | | 115-199 |
| 0087 | 24 | | GK | | 3-0 | 32-61-12 | D03210A | G02 | | | TB0182Y | A012 | BJ | | 001-099 |
| 0087 | 22 | | GA | | 3-0 | 32-61-12 | D03210A | G02 | | | TB0182Y | A012 | BJ | | 115-199 |
| 0088 | 24 | | GK | | 3-0 | 32-61-12 | D03210E | J03 | | | TB0182Y | C009 | BJ | | ALL |
| 0089 | 24 | | GK | | 4-0 | 32-61-12 | D41363J | 7 | | | TB0182Y | C009 | BJ | | 001-099 |
| 0089 | 24 | | GK | | 3-0 | 32-61-12 | D41363J | 7 | | | TB0182Y | C009 | BJ | | 115-199 |
| 0090 | 22 | | GA | | 3-0 | 32-61-21 | D41363J | 8 | | | D03210E | C05 | | | ALL |
| 0091 | 22 | | GA | | 3-0 | 32-61-21 | TB0182Y | C018 | BJ | | D03210E | B05 | | | ALL |
| 0092 | 22 | | GA | | 3-0 | 32-61-21 | D41363J | 10 | | | D03210E | A05 | | | ALL |
| 0093 | 22 | | GA | | 3-0 | 32-61-21 | D03210A | C05 | | | D41311J | 4 | | | ALL |
| 0094 | 22 | | GA | | 3-0 | 32-61-21 | D03210A | B05 | | | D41311J | 5 | | | ALL |
| 0095 | 22 | | GA | | 3-0 | 32-61-21 | D03210A | A05 | | | D41311J | 6 | | | ALL |
| 0096 | 22 | | GA | | 1-0 | 28-41-11 | D02440A | E09 | | | D02440A | C09 | | | 001-003, 005, 009-099 |
| 0096 | 22 | | GA | | 1-0 | 28-41-11 | D02440A | A09 | | | D02440A | C09 | | | 004, 006-008 |
| 0096 | 24 | | GK | | 1-0 | 28-41-11 | D02440A | A09 | | | D02440A | C09 | | | 115-199 |
| 0099 | 22 | | GA | | 3-0 | 28-41-11 | D41610J | 33 | | | D41614J | 2 | | | 001-099 |
| 0099 | 24 | | GK | | 4-0 | 28-41-11 | D41610J | 33 | | | D41614J | 2 | | | 115-199 |
| 0103 | 24 | | GK | | 3-0 | 28-41-14 | D02440A | K09 | | | D41610J | 32 | | | 001-099 |
| 0103 | 24 | | GK | | 4-0 | 28-41-14 | D02440A | K09 | | | D41610J | 32 | | | 115-199 |
| 0105 | 22 | | GA | | 3-0 | 28-41-11 | D41610J | 34 | | | D41614J | 4 | | | 001-099 |
| 0105 | 24 | | GK | | 4-0 | 28-41-11 | D41610J | 34 | | | D41614J | 4 | | | 115-199 |
| 0106 | 22 | | GA | | 4-0 | 32-61-21 | D42016J | 18 | | | D41363J | 9 | | | 001-099 |
| 0106 | 22 | | GA | | 5-0 | 32-61-21 | D41363J | 9 | | | D42016J | 18 | | | 115-199 |
| 0107 | 22 | | GA | | 2-0 | 31-51-42 | D41445J | 1 | | | SM00003 | | WI | | 001, 003-099 |
| 0107 | 22 | | GA | | 2-0 | 31-51-42 | D41445J | 1 | | | SM00003 | | W | | 002 |
| 0107 | 22 | | GA | | 4-0 | 31-51-42 | D41445J | 1 | | | SM00003 | | WI | | 115-199 |
| 0140 | 24 | | GK | | 4-0 | 32-41-11 | TB0182Y | C004 | BJ | | D40680J | 10 | | | ALL |
| 0141 | 24 | | GK | | 4-0 | 32-41-11 | TB0182Y | C004 | BJ | | D42018J | 26 | | | 001-099 |
| 0141 | 24 | | GK | | 3-0 | 32-41-11 | TB0182Y | C004 | BJ | | D42018J | 26 | | | 115-199 |
| 0142 | 24 | | GK | | 4-0 | 32-41-11 | D42169J | 9 | | | D42018J | 27 | | | 001-099 |
| 0142 | 24 | | GK | | 5-0 | 32-41-11 | D42169J | 9 | | | D42018J | 27 | | | 115-199 |
| 0143 | 24 | | GK | | 3-0 | 32-41-11 | GD01883 | AC.. | 2 | | D42018J | 28 | | | ALL |
| 0144 | 24 | | GK | | 4-0 | 32-41-11 | D42169J | 10 | | | TB0182Y | A006 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 4

Dec 18/2007



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------|---------|-------|------|------|--------|---------|------|-------------|------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W1280 | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | |
| 0145 | 24 | | GK | 4-0 | 32-41-11 | D42169J | | 8 | | | TB0182Y | C004 | BJ | | ALL |
| 0146 | 24 | | GK | 4-0 | 32-41-11 | D42018J | | 7 | | | TB0182Y | A006 | BJ | | 001-099 |
| 0146 | 24 | | GK | 3-0 | 32-41-11 | D42018J | | 37 | | | TB0182Y | A006 | BJ | | 115-199 |
| 0147 | 22 | | GA | 3-0 | 78-34-11 | D03210B | | H12 | | | D42012J | 5 | | | ALL |
| 0148 | 22 | | GA | 5-0 | 32-61-11 | D03210E | | J07 | | | D40702J | 1 | | | 001-099 |
| 0148 | 22 | | GA | 4-0 | 32-61-11 | D03210E | | J07 | | | D40702J | 1 | | | 115-199 |
| 0149 | 22 | | GA | 4-0 | 78-34-11 | D03210B | | B14 | | | GD01882 | DC.. | 2 | | 001-099 |
| 0149 | 22 | | GA | 3-0 | 78-34-11 | D03210B | | B14 | | | GD01882 | DC.. | 2 | | 115-199 |
| 0150 | 22 | | GA | 3-0 | 78-34-11 | D03210B | | A14 | | | D42012J | 21 | | | 001-002 |
| 0150 | 22 | | GA | 3-0 | 78-34-11 | D03210B | | A14 | | | D42012J | 9 | | | 003-099 |
| 0150 | 22 | | GA | 4-0 | 78-34-11 | D03210B | | A14 | | | D42012J | 23 | | | 115-199 |
| 0151 | 24 | | GK | 4-0 | 32-41-11 | D42014J | | 12 | | | TB0182Y | A006 | BJ | | 001-099 |
| 0151 | 24 | | GK | 3-0 | 32-41-11 | D42014J | | 12 | | | TB0182Y | A006 | BJ | | 115-199 |
| 0152 | 22 | | GA | 4-0 | 78-34-21 | D03210D | | H13 | | | D42014J | 2 | | | ALL |
| 0153 | 22 | | GA | 3-0 | 32-61-11 | D41445J | | 27 | | | TB0182Y | C017 | BJ | | ALL |
| 0154 | 22 | | GA | 3-0 | 78-34-21 | D03210D | | B14 | | | GD01882 | DC.. | 2 | | ALL |
| 0155 | 22 | | GA | 4-0 | 78-34-21 | D03210D | | A14 | | | D42014J | 21 | | | ALL |
| 0156 | 22 | | GA | 4-0 | 25-66-11 | D40702J | | 7 | | | TB0182Y | A014 | BJ | | 001-099 |
| 0156 | 22 | | GA | 3-0 | 25-66-11 | D40702J | | 7 | | | TB0182Y | A014 | BJ | | 115-199 |
| 0157 | 22 | | GA | 3-0 | 25-66-11 | D41706J | | 1 | | | TB0182Y | A014 | BJ | | ALL |
| 0158 | 22 | | GA | 4-0 | 25-66-11 | D41708J | | 1 | | | TB0182Y | A014 | BJ | | 001-099 |
| 0158 | 22 | | GA | 3-0 | 25-66-11 | D41708J | | 1 | | | TB0182Y | A014 | BJ | | 115-199 |
| 0161 | 20 | | GA | 3-0 | 28-41-11 | TB0182Y | A034 | BJ | | | D41876J | 16 | | | ALL |
| 0168 | 24 | | GK | 4-0 | 28-41-11 | D02440A | | C14 | | | D41618J | 19 | | | 001-099 |
| 0168 | 24 | | GK | 3-0 | 28-41-11 | D02440A | | C14 | | | D41618J | 19 | | | 115-199 |
| 0169 | 24 | | GK | 4-0 | 28-41-13 | D02440A | | H14 | | | D41618J | 18 | | | 001-099 |
| 0169 | 24 | | GK | 3-0 | 28-41-13 | D02440A | | H14 | | | D41618J | 18 | | | 115-199 |
| 0174 | 22 | | GA | 3-0 | 28-21-11 | D02440C | | C09 | | | GD01884 | DC.. | 2 | | 001-099 |
| 0174 | 22 | | GA | 4-0 | 28-21-11 | D02440C | | C09 | | | GD01888 | DC.. | 2 | | 115-199 |
| 0176 | 22 | | GA | 3-0 | 28-21-11 | D02440C | | H09 | | | GD01884 | DC.. | 2 | | 001-099 |
| 0176 | 22 | | GA | 4-0 | 28-21-11 | D02440C | | H09 | | | GD01888 | DC.. | 2 | | 115-199 |
| 0180 | 22 | | GA | 4-0 | 28-21-22 | D02440B | | A04 | | | TB0182Y | A010 | BJ | | ALL |
| 0181 | 22 | | GA | 3-0 | 28-21-22 | D02440B | | H09 | | | D41614J | 34 | | | ALL |
| 0182 | 22 | | GA | 3-0 | 28-21-22 | D02440A | | H09 | | | D41614J | 35 | | | ALL |
| 0183 | 22 | | GA | 4-0 | 28-21-22 | D02440A | | A04 | | | TB0182Y | C010 | BJ | | ALL |
| 0189 | 24 | | GK | 4-0 | 31-51-21 | D42012J | | 7 | | | D41311J | 7 | | | ALL |
| 0190 | 24 | | GK | 4-0 | 31-51-21 | D42012J | | 8 | | | D41311J | 8 | | | ALL |
| 0191 | 24 | | GK | 2-0 | 31-51-21 | D42016J | | 13 | | | D41445J | 12 | | | 001-099 |
| 0191 | 24 | | GK | 4-0 | 31-51-21 | D42016J | | 13 | | | D41445J | 12 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0192 | 24 | | GK | | 4-0 | 31-51-21 | D42018J | 11 | | | D41363J | 1 | | | ALL |
| 0193 | 24 | | GK | | 4-0 | 31-51-21 | D42018J | 12 | | | D41363J | 2 | | | ALL |
| 0194 | 22 | | GA | | 4-0 | 32-09-11 | TB0182Y | A004 | BJ | | D41610J | 30 | | | 115-199 |
| 0195 | 22 | | GA | | 4-0 | 32-09-11 | TB0182Y | A004 | BJ | | D41610J | 3 | | | 115-199 |
| 0196 | 22 | | GA | | 3-0 | 32-09-11 | D03210D | B12 | | | GD01882 | DC.. | 2 | | 001-099 |
| 0196 | 22 | | GA | | 3-0 | 32-01-11 | D03210D | B12 | | | GD01882 | DC.. | 2 | | 115-199 |
| 0197 | 22 | | GA | | 3-0 | 32-09-11 | D03210D | D12 | | | GD01882 | ST.. | 2 | | 001-099 |
| 0197 | 22 | | GA | | 3-0 | 32-01-11 | D03210D | D12 | | | GD01882 | ST.. | 2 | | 115-199 |
| 0198 | 22 | | GA | | 5-0 | 32-09-11 | D03210D | A12 | | | D40702J | 8 | | | 001-099 |
| 0198 | 22 | | GA | | 4-0 | 32-01-11 | D03210D | A12 | | | D40702J | 8 | | | 115-199 |
| 0199 | 22 | | GA | | 1-0 | 52-71-21 | D03210B | D04 | | | D03210B | J04 | | | 001-099 |
| 0199 | 22 | | GA | | 1-0 | 52-71-21 | D03210B | F07 | | | D03210B | E04 | | | 115-199 |
| 0200 | 22 | | GA | | 4-0 | 32-61-11 | D03210A | K07 | | | GD01882 | DC.. | 2 | | 001-099 |
| 0200 | 22 | | GA | | 3-0 | 32-61-11 | D03210A | K07 | | | GD01882 | DC.. | 2 | | 115-199 |
| 0201 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | C08 | | | D41610J | 2 | | | ALL |
| 0202 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | B08 | | | D41610J | 3 | | | 001-099 |
| 0202 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | B08 | | | TB0182Y | A004 | BJ | | 115-199 |
| 0203 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | D08 | | | D41610J | 4 | | | ALL |
| 0204 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | A08 | | | D41610J | 5 | | | ALL |
| 0205 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | E08 | | | D41610J | 6 | | | ALL |
| 0206 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | A06 | | | TB0182Y | C014 | BJ | | ALL |
| 0207 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | B06 | | | D41610J | 8 | | | ALL |
| 0208 | 22 | | GA | | 3-0 | 32-61-11 | D03210A | J07 | | | TB0182Y | C017 | BJ | | ALL |
| 0209 | 22 | | GA | | 4-0 | 32-61-11 | D03210E | K07 | | | GD01882 | DC.. | 2 | | 001-099 |
| 0209 | 22 | | GA | | 3-0 | 32-61-11 | D03210E | K07 | | | GD01882 | DC.. | 2 | | 115-199 |
| 0210 | 22 | | GA | | 3-0 | 32-09-12 | D03210E | H08 | | | D41614J | 44 | | | ALL |
| 0211 | 22 | | GA | | 3-0 | 32-09-12 | D03210E | C08 | | | D41614J | 45 | | | ALL |
| 0212 | 22 | | GA | | 3-0 | 32-09-12 | D03210E | D08 | | | D41614J | 46 | | | ALL |
| 0213 | 22 | | GA | | 3-0 | 32-09-12 | D03210E | G08 | | | D41614J | 47 | | | ALL |
| 0214 | 22 | | GA | | 3-0 | 32-09-12 | D03210E | G06 | | | TB0182Y | C005 | BJ | | ALL |
| 0215 | 22 | | GA | | 3-0 | 32-09-12 | D03210E | E08 | | | D41614J | 49 | | | ALL |
| 0216 | 22 | | GA | | 3-0 | 32-61-11 | TB0182Y | C017 | BJ | | D41445J | 29 | | | ALL |
| 0217 | 22 | | GA | | 3-0 | 32-09-12 | D03210E | H06 | | | D41614J | 51 | | | ALL |
| 0219 | 22 | | GA | | 4-0 | 28-21-22 | D41614J | 37 | | | TB0182Y | A010 | BJ | | ALL |
| 0220 | 22 | | GA | | 4-0 | 28-21-22 | D02440B | H04 | | | TB0182Y | A010 | BJ | | ALL |
| 0221 | 22 | | GA | | 4-0 | 28-21-22 | D02440A | H04 | | | TB0182Y | C010 | BJ | | ALL |
| 0222 | 22 | | GA | | 4-0 | 28-21-22 | D41614J | 36 | | | TB0182Y | C010 | BJ | | ALL |
| 0223 | 22 | | GA | | 3-0 | 32-09-12 | D42060J | 30 | | | D41634J | 14 | | | ALL |
| 0224 | 22 | | GA | | 3-0 | 32-09-12 | TB0182Y | C005 | BJ | | D41634J | 15 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | |
| 0224 | 22 | GA | | | 4-0 | 32-09-12 | TB0182Y | C005 | BJ | | D41634J | 15 | | | 115-199 |
| 0228 | 22 | GA | | | 4-0 | 28-41-11 | D02440A | B09 | | | GD01882 | ST.. | 2 | *1 | 001-099 |
| 0228 | 22 | GA | | | 4-0 | 28-41-11 | D02440A | B09 | | | GD01882 | ST.. | 2 | | 115-199 |
| 0238 | 24 | GK | | | 3-0 | 33-24-11 | D03210A | E06 | | | D41876J | 3 | | | 001-099 |
| 0238 | 22 | GA | | | 3-0 | 33-24-11 | D03210A | E06 | | | D41876J | 3 | | | 115-199 |
| 0239 | 22 | GA | | | 3-0 | 32-61-12 | D03210A | D06 | | | TB0182Y | A008 | BJ | | 001-099 |
| 0239 | 22 | GA | | | 3-0 | 32-61-11 | D03210A | D06 | | | TB0182Y | A008 | BJ | | 115-199 |
| 0249 | 20 | GA | | | 4-0 | 28-21-11 | TB0182Y | A034 | BJ | | D42012J | 15 | | | 001-099 |
| 0249 | 22 | GA | | | 5-0 | 28-21-11 | TB0182Y | A034 | BJ | | D42012J | 15 | | | 115-199 |
| 0250 | 20 | GA | | | 4-0 | 28-21-11 | TB0182Y | C034 | BJ | | D41614J | 28 | | | 001-099 |
| 0250 | 22 | GA | | | 3-0 | 28-21-11 | TB0182Y | C034 | BJ | | D41614J | 28 | | | 115-199 |
| 0265 | 22 | GA | | | 3-0 | 28-21-21 | D41614J | 29 | | | D41876J | 1 | | | 001-099 |
| 0265 | 20 | GA | | | 3-0 | 28-21-21 | D41614J | 29 | | | D41876J | 1 | | | 115-199 |
| 0266 | 22 | GA | | | 4-0 | 32-42-11 | D03210E | K06 | | | D41445J | 10 | | | 001-099 |
| 0266 | 22 | GA | | | 3-0 | 32-42-11 | D03210E | K06 | | | D42016J | 24 | | | 115-199 |
| 0267 | 22 | GA | | | 4-0 | 32-42-11 | D03210A | F06 | | | D41445J | 11 | | | 001-099 |
| 0267 | 22 | GA | | | 3-0 | 32-42-11 | D03210A | F06 | | | D42016J | 23 | | | 115-199 |
| 0269 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | E04 | | | D41268J | 17 | | | 001-099 |
| 0269 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | E04 | | | D41636J | 11 | | | 115-199 |
| 0270 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | C01 | | | D41268J | 3 | | | 001-099 |
| 0270 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | C01 | | | D41636J | 12 | | | 115-199 |
| 0271 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | D01 | | | D41268J | 4 | | | 001-099 |
| 0271 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | D01 | | | D41636J | 13 | | | 115-199 |
| 0272 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | E01 | | | D41268J | 5 | | | 001-099 |
| 0272 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | E01 | | | D41636J | 14 | | | 115-199 |
| 0273 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | F01 | | | D41268J | 6 | | | 001-099 |
| 0273 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | F01 | | | D41636J | 15 | | | 115-199 |
| 0274 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | C02 | | | D41268J | 7 | | | 001-099 |
| 0274 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | C02 | | | D41636J | 16 | | | 115-199 |
| 0275 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | D02 | | | D41268J | 8 | | | 001-099 |
| 0275 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | D02 | | | D41636J | 17 | | | 115-199 |
| 0276 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | E02 | | | D41268J | 9 | | | 001-099 |
| 0276 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | E02 | | | D41636J | 18 | | | 115-199 |
| 0277 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | F02 | | | D41268J | 10 | | | 001-099 |
| 0277 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | F02 | | | D41636J | 19 | | | 115-199 |
| 0278 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | C03 | | | D41268J | 11 | | | 001-099 |
| 0278 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | C03 | | | D41636J | 20 | | | 115-199 |
| 0279 | 24 | GK | | | 5-0 | 28-41-21 | D02440A | D03 | | | D41268J | 12 | | | 001-099 |
| 0279 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | D03 | | | D41636J | 21 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0280 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | E04 | | D41270J | 17 | | | 001-099 |
| 0280 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | E04 | | D41620J | 1 | | | 115-199 |
| 0281 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | C01 | | D41270J | 3 | | | 001-099 |
| 0281 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | C01 | | D41620J | 2 | | | 115-199 |
| 0282 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | D01 | | D41270J | 4 | | | 001-099 |
| 0282 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | D01 | | D41620J | 3 | | | 115-199 |
| 0283 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | E01 | | D41270J | 5 | | | 001-099 |
| 0283 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | E01 | | D41620J | 4 | | | 115-199 |
| 0284 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | F01 | | D41270J | 6 | | | 001-099 |
| 0284 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | F01 | | D41620J | 5 | | | 115-199 |
| 0285 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | C02 | | D41270J | 7 | | | 001-099 |
| 0285 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | C02 | | D41620J | 6 | | | 115-199 |
| 0286 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | D02 | | D41270J | 8 | | | 001-099 |
| 0286 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | D02 | | D41620J | 7 | | | 115-199 |
| 0287 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | E02 | | D41270J | 9 | | | 001-099 |
| 0287 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | E02 | | D41620J | 8 | | | 115-199 |
| 0288 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | F02 | | D41270J | 10 | | | 001-099 |
| 0288 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | F02 | | D41620J | 9 | | | 115-199 |
| 0289 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | C03 | | D41270J | 11 | | | 001-099 |
| 0289 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | C03 | | D41620J | 10 | | | 115-199 |
| 0290 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | | D03 | | D41270J | 12 | | | 001-099 |
| 0290 | 24 | | GK | | 3-0 | 28-41-31 | | D02440B | | D03 | | D41620J | 11 | | | 115-199 |
| 0291 | 24 | | GK | | 5-0 | 28-41-41 | | D02440B | | E10 | | D42226J | 7 | | | 001-099 |
| 0291 | 24 | | GK | | 3-0 | 28-41-41 | | D02440B | | E10 | | D41620J | 17 | | | 115-199 |
| 0292 | 24 | | GK | | 5-0 | 28-41-41 | | D02440B | | D11 | | D42226J | 4 | | | 001-099 |
| 0292 | 24 | | GK | | 3-0 | 28-41-41 | | D02440B | | D11 | | D41620J | 12 | | | 115-199 |
| 0293 | 24 | | GK | | 5-0 | 28-41-41 | | D02440B | | E11 | | D42226J | 5 | | | 001-099 |
| 0293 | 24 | | GK | | 3-0 | 28-41-41 | | D02440B | | E11 | | D41620J | 13 | | | 115-199 |
| 0294 | 24 | | GK | | 5-0 | 28-41-41 | | D02440B | | F11 | | D42226J | 6 | | | 001-099 |
| 0294 | 24 | | GK | | 3-0 | 28-41-41 | | D02440B | | F11 | | D41620J | 14 | | | 115-199 |
| 0296 | 24 | | GK | | 5-0 | 28-41-41 | | D02440B | | F10 | | D42226J | 9 | | | 001-099 |
| 0296 | 24 | | GK | | 3-0 | 28-41-41 | | D02440B | | F10 | | D41620J | 16 | | | 115-199 |
| 0297 | 24 | | GK | | 5-0 | 28-41-41 | | D02440A | | D10 | | D42224J | 8 | | | 001-099 |
| 0297 | 24 | | GK | | 3-0 | 28-41-41 | | D02440A | | D10 | | D41636J | 26 | | | 115-199 |
| 0298 | 24 | | GK | | 5-0 | 28-41-41 | | D02440A | | E10 | | D42224J | 4 | | | 001-099 |
| 0298 | 24 | | GK | | 3-0 | 28-41-41 | | D02440A | | E10 | | D41636J | 27 | | | 115-199 |
| 0299 | 24 | | GK | | 5-0 | 28-41-41 | | D02440A | | D11 | | D42224J | 5 | | | 001-099 |
| 0299 | 24 | | GK | | 3-0 | 28-41-41 | | D02440A | | D11 | | D41636J | 28 | | | 115-199 |
| 0300 | 24 | | GK | | 5-0 | 28-41-41 | | D02440A | | E11 | | D42224J | 6 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0300 | 24 | | GK | | 3-0 | 28-41-41 | D02440A | E11 | | | D41636J | 29 | | | 115-199 |
| 0301 | 24 | | GK | | 5-0 | 28-41-41 | D02440B | D10 | | | D42224J | 7 | | | 001-099 |
| 0301 | 24 | | GK | | 3-0 | 28-41-41 | D02440B | D10 | | | D41636J | 30 | | | 115-199 |
| 0303 | 22 | | GA | | 3-0 | 32-09-11 | D41620J | 21 | | | D41610J | 10 | | | 001-099 |
| 0303 | 22 | | GA | | 4-0 | 32-09-11 | D41620J | 35 | | | D41610J | 10 | | | 115-199 |
| 0304 | 22 | | GA | | 3-0 | 32-09-11 | D41610J | 7 | | | TB0182Y | C014 | BJ | | 001-099 |
| 0304 | 22 | | GA | | 4-0 | 32-09-11 | D41610J | 7 | | | TB0182Y | C014 | BJ | | 115-199 |
| 0305 | 22 | | GA | | 3-0 | 32-09-11 | D41620J | 15 | | | TB0182Y | C014 | BJ | | 001-099 |
| 0305 | 22 | | GA | | 4-0 | 32-09-11 | D41620J | 15 | | | TB0182Y | C014 | BJ | | 115-199 |
| 0306 | 22 | | GA | | 3-0 | 32-09-11 | D03210A | C04 | | | D41610J | 9 | | | ALL |
| 0309 | 22 | | GA | | 4-0 | 32-09-12 | D41614J | 48 | | | TB0182Y | C005 | BJ | | ALL |
| 0311 | 22 | | GA | | 3-0 | 32-09-12 | D03210E | H03 | | | D41614J | 52 | | | ALL |
| 0315 | 24 | | GK | | 5-0 | 28-41-31 | D02440B | E03 | | | D41270J | 13 | | | 001-099 |
| 0315 | 24 | | GK | | 3-0 | 28-41-31 | D02440B | E03 | | | D41620J | 36 | | | 115-199 |
| 0316 | 24 | | GK | | 5-0 | 28-41-31 | D02440B | F03 | | | D41270J | 14 | | | 001-099 |
| 0316 | 24 | | GK | | 3-0 | 28-41-31 | D02440B | F03 | | | D41620J | 37 | | | 115-199 |
| 0317 | 24 | | GK | | 5-0 | 28-41-21 | D02440A | E03 | | | D41268J | 13 | | | 001-099 |
| 0317 | 24 | | GK | | 3-0 | 28-41-21 | D02440A | E03 | | | D41636J | 22 | | | 115-199 |
| 0318 | 24 | | GK | | 5-0 | 28-41-21 | D02440A | F03 | | | D41268J | 14 | | | 001-099 |
| 0318 | 24 | | GK | | 3-0 | 28-41-21 | D02440A | F03 | | | D41636J | 25 | | | 115-199 |
| 0319 | 22 | | GA | | 3-0 | 52-34-11 | D03210D | K03 | | | GD01882 | DC.. | 2 | * | 001-099 |
| 0319 | 22 | | GA | | 3-0 | 52-34-11 | D03210D | K03 | | | GD01882 | DC.. | 2 | | 115-199 |
| 0320 | 24 | | GK | | 3-0 | 31-31-31 | D42018J | 31 | | | D41445J | 20 | | | 115-199 |
| 0321 | 24 | | GK | | 3-0 | 31-31-31 | D42018J | 32 | | | D41445J | 21 | | | 115-199 |
| 0322 | 24 | | GK | | 3-0 | 31-31-31 | D42018J | 33 | | | D41445J | 22 | | | 115-199 |
| 0323 | 24 | | GK | | 4-0 | 31-31-31 | D41445J | 16 | | | SM00003 | | WI | | 115-199 |
| 0324 | 24 | | GK | | 3-0 | 31-31-31 | D41445J | 17 | | | D03210E | H05 | | | 115-199 |
| 0325 | 24 | | GK | | 3-0 | 31-31-31 | D41445J | 18 | | | D03210E | J08 | | | 115-199 |
| 0326 | 22 | | GA | | 2-0 | 23-31-13 | D40924J | 5 | | | D41445J | 25 | | | 001-099 |
| 0326 | 22 | | GA | | 3-0 | 23-31-13 | D40924J | 5 | | | D41445J | 25 | | | 115-199 |
| 0327 | 22 | | GA | | 2-0 | 23-31-13 | D40924J | 6 | | | D41445J | 24 | | | 001-099 |
| 0327 | 22 | | GA | | 3-0 | 23-31-13 | D40924J | 6 | | | D41445J | 24 | | | 115-199 |
| 0328 | 22 | | GA | | 3-0 | 27-11-11 | D41610J | 17 | | | D40996J | 1 | | | 001-009, 115-199 |
| 0328 | 22 | | GA | | 3-0 | 27-11-11 | D41610J | 17 | | | SM00005 | | WI | | 010-099 |
| 0329 | 22 | | GA | | 3-0 | 27-11-11 | D41610J | 18 | | | D40996J | 2 | | | 001-009, 115-199 |
| 0329 | 22 | | GA | | 3-0 | 27-11-11 | D41610J | 18 | | | SM00006 | | WI | | 010-099 |
| 0330 | 24 | | GK | | 3-0 | 34-46-11 | D41311J | 10 | | | D40996J | 11 | | | ALL |
| 0333 | 24 | | GK | | 4-0 | 32-41-11 | D42169J | 11 | | | GD01883 | AC.. | 2 | | ALL |
| 0334 | 22 | | GA | | 2-0 | 32-44-11 | D42016J | 19 | | | D42018J | 20 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0334 | 22 | | GA | | 3-0 | 32-44-11 | D42016J | 19 | | | D42018J | 20 | | | 115-199 |
| 0335 | 22 | | GA | | 2-0 | 32-44-11 | D42016J | 20 | | | D42018J | 21 | | | 001-099 |
| 0335 | 22 | | GA | | 3-0 | 32-44-11 | D42016J | 20 | | | D42018J | 21 | | | 115-199 |
| 0336 | 22 | | GA | | 2-0 | 32-44-11 | D42016J | 22 | | | D42018J | 22 | | | 001-099 |
| 0336 | 22 | | GA | | 3-0 | 32-44-11 | D42016J | 22 | | | D42018J | 22 | | | 115-199 |
| 0337 | 22 | | GA | | 2-0 | 32-44-11 | D42016J | 21 | | | D42018J | 23 | | | 001-099 |
| 0337 | 22 | | GA | | 3-0 | 32-44-11 | D42016J | 21 | | | D42018J | 23 | | | 115-199 |
| 0339 | 24 | | GK | | 1-0 | 52-71-21 | TB0182Y | A017 | BJ | | TB0182A | C019 | 2 | | 115-199 |
| 0340 | 24 | | GK | | 3-0 | 32-61-12 | D03210E | F06 | | | TB0182C | C028 | 2 | | ALL |
| 0341 | 22 | | GA | | 4-0 | 28-41-13 | D40996J | 25 | | | TB0182Z | 16 | BJ | | 001-099 |
| 0341 | 20 | | GA | | 4-0 | 28-41-13 | D40996J | 25 | | | TB0182Z | 16 | BJ | | 115-199 |
| 0342 | 22 | | GA | | 4-0 | 28-41-13 | D40996J | 26 | | | TB0182Z | 16 | BJ | | 001-099 |
| 0342 | 20 | | GA | | 4-0 | 28-41-13 | D40996J | 26 | | | TB0182Z | 16 | BJ | | 115-199 |
| 0346 | 22 | | GA | | 3-0 | 32-09-11 | D41610J | 14 | | | D03210A | H05 | | | ALL |
| 0347 | 22 | | GA | | 4-0 | 32-09-12 | D42060J | 26 | | | D03210E | A04 | | | 001-002 |
| 0347 | 22 | | GA | | 4-0 | 32-09-12 | D42060J | 24 | | | D03210E | A06 | | | 003-099 |
| 0347 | 22 | | GA | | 3-0 | 32-09-12 | D42060J | 24 | | | D03210E | A06 | | | 115-199 |
| 0348 | 22 | | GA | | 4-0 | 32-09-12 | D42060J | 25 | | | D03210E | K05 | | | 001-099 |
| 0348 | 22 | | GA | | 3-0 | 32-09-12 | D42060J | 25 | | | D03210E | K05 | | | 115-199 |
| 0349 | 22 | | GA | | 4-0 | 32-09-12 | D42060J | 24 | | | D03210E | E06 | | | 001-002 |
| 0349 | 22 | | GA | | 4-0 | 32-09-12 | D42060J | 26 | | | D03210E | E06 | | | 003-099 |
| 0349 | 22 | | GA | | 3-0 | 32-09-12 | D42060J | 26 | | | D03210E | E06 | | | 115-199 |
| 0351 | 24 | | GK | | 0-6 | 28-21-22 | D02440A | D08 | | | SM00001 | | WI | | 001-099 |
| 0351 | 24 | | GK | | 0-6 | 28-21-22 | D02440A | D08 | | | SM00001 | | 9 | | 115-199 |
| 0352 | 22 | | GA | | 2-0 | 29-21-31 | D42016J | 9 | | | D42018J | 24 | | | 001-099 |
| 0352 | 22 | | GA | | 3-0 | 29-21-31 | D42016J | 9 | | | D42018J | 24 | | | 115-199 |
| 0353 | 22 | | GA | | 2-0 | 29-21-31 | D42016J | 10 | | | D42018J | 30 | | | 001-099 |
| 0353 | 22 | | GA | | 3-0 | 29-21-31 | D42016J | 10 | | | D42018J | 30 | | | 115-199 |
| 0354 | 24 | | GK | | 3-0 | 52-71-21 | D03210B | E06 | | | TB0182Y | A017 | BJ | | 115-199 |
| 0355 | 24 | | GK | | 3-0 | 52-71-21 | D40680J | 2 | | | TB0182A | A019 | 2 | | 115-199 |
| 0356 | 24 | | GK | | 3-0 | 52-71-21 | D41445J | 19 | | | TB0182Y | A017 | BJ | | 115-199 |
| 0357 | 20 | | GA | | 3-0 | 33-45-11 | D40996J | 29 | | | D41620J | 20 | | | 001-099 |
| 0357 | 20 | | GA | | 3-0 | 33-45-11 | D40996J | 19 | | | D41620J | 20 | | | 115-199 |
| 0358 | 20 | | GA | | 3-0 | 33-45-11 | D40996J | 20 | | | D41618J | 8 | | | 001-099 |
| 0358 | 20 | | GA | | 3-0 | 33-45-11 | D40996J | 20 | | | D41618J | 1 | | | 115-199 |
| 0359 | 22 | | GA | | 4-0 | 28-41-13 | D02440A | J08 | | | TB0182Z | 16 | BJ | | ALL |
| 0360 | 20 | | GA | | 5-0 | 28-25-11 | D42012J | 14 | | | D42016J | 26 | | | ALL |
| 0361 | 22 | | GA | | 0-10 | 34-61-24 | D41363J | | | AA | GDX0002 | ST.. | E | | 001-099 |
| 0361 | 22 | | GA | | 4-0 | 34-61-24 | D41363J | | | AA | GD01888 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 10

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | | | | | | | | | | | | | | | |
| | | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | |
| 0362 | 22 | GA | | | 0-10 | 34-61-14 | D41311J | | | AB | GDX0001 | ST.. | E | | 001-009 |
| 0362 | 22 | GA | | | 3-0 | 34-61-14 | D41311J | | | AB | GD01888 | ST.. | 2 | | 115-199 |
| 0363 | 22 | GA | | | 3-0 | 25-66-11 | D41876J | 30 | | | TB0182Y | A014 | BJ | | 001-099 |
| 0363 | 22 | GA | | | 4-0 | 25-66-11 | D41876J | 30 | | | TB0182Y | A014 | BJ | | 115-199 |
| 0364 | 20 | GA | | | 0-18 | 28-41-31 | D41620J | 22 | | | GD01888 | ST.. | 2 | | 115-199 |
| 0365 | 20 | GA | | | 0-18 | 28-41-41 | D41620J | 29 | | | GD01888 | ST.. | 2 | | 115-199 |
| 0366 | 20 | GA | | | 0-36 | 28-41-31 | D42222J | 2 | | | GD01882 | ST.. | 2 | | 115-199 |
| 0367 | 20 | GA | | | 0-36 | 28-41-41 | D42226J | 2 | | | GD01882 | ST.. | 2 | | 115-199 |
| 0368 | 20 | GA | | | 0-18 | 28-41-21 | D41636J | 9 | | | GD01888 | ST.. | 2 | | 115-199 |
| 0369 | 20 | GA | | | 0-18 | 28-41-41 | D41636J | 31 | | | GD01888 | ST.. | 2 | | 115-199 |
| 0370 | 20 | GA | | | 0-36 | 28-41-21 | D42220J | 2 | | | GD01883 | ST.. | 2 | | 115-199 |
| 0371 | 20 | GA | | | 0-36 | 28-41-41 | D42224J | 2 | | | GD01883 | ST.. | 2 | | 115-199 |
| 0372 | 22 | GA | | | 2-0 | 32-42-11 | D41445J | 26 | | | D42014J | 18 | | | 001-099 |
| 0372 | 22 | GA | | | 4-0 | 32-42-11 | D41445J | 26 | | | D42014J | 18 | | | 115-199 |
| 0373 | 24 | GK | | | 4-0 | 32-61-12 | D41363J | 31 | | | TB0182Y | A018 | BJ | | 001-099 |
| 0373 | 22 | GA | | | 3-0 | 32-61-11 | D41363J | 31 | | | TB0182Y | A018 | BJ | | 115-199 |
| 0374 | 24 | GK | | | 4-0 | 32-61-12 | D41363J | 16 | | | TB0182Y | A012 | BJ | | 001-099 |
| 0374 | 22 | GA | | | 3-0 | 32-61-11 | D41363J | 32 | | | TB0182Y | A012 | BJ | | 115-199 |
| 0375 | 24 | GK | | | 3-0 | 32-61-12 | D41311J | 30 | | | TB0182Y | A012 | BJ | | 001-099 |
| 0375 | 22 | GA | | | 3-0 | 32-61-12 | D41311J | 30 | | | TB0182Y | A012 | BJ | | 115-199 |
| 0376 | 24 | GK | | | 4-0 | 32-61-12 | D41363J | 6 | | | TB0182Y | A018 | BJ | | 001-099 |
| 0376 | 22 | GA | | | 4-0 | 32-61-12 | D41363J | 6 | | | TB0182Y | A018 | BJ | | 115-199 |
| 0377 | 22 | GA | | | 2-0 | 29-22-11 | D42018J | 29 | | | D42016J | 28 | | | 001-099 |
| 0377 | 22 | GA | | | 3-0 | 29-22-11 | D42018J | 29 | | | D42016J | 28 | | | 115-199 |
| 0379 | 22 | GA | | | 3-0 | 32-61-12 | D41311J | 18 | | | TB0182Y | C008 | BJ | | 001-099 |
| 0379 | 22 | GA | | | 3-0 | 32-61-12 | D41311J | 38 | | | TB0182Y | C008 | BJ | | 115-199 |
| 0380 | 22 | GA | | | 3-0 | 76-11-21 | D03210E | B07 | | | D42060J | 1 | | | 115-199 |
| 0381 | 22 | GA | | | 3-0 | 76-11-21 | D41311J | 1 | | | D03210A | B07 | | | 001-099 |
| 0381 | 22 | GA | | | 3-0 | 76-11-21 | D03210A | B07 | | | D41311J | 1 | | | 115-199 |
| 0382 | 22 | GA | | | 4-0 | 76-11-21 | D03210E | B07 | | | D42060J | 1 | | | 001-099 |
| 0400 | 22 | GA | | | 4-0 | 28-41-21 | D02440A | K04 | | | GD01883 | DC.. | 2 | | 001-099 |
| 0400 | 24 | GK | | | 4-0 | 28-41-21 | D02440A | K04 | | | GD01883 | DC.. | 2 | | 115-199 |
| 0401 | 22 | GA | | | 3-0 | 29-11-12 | D41620J | 25 | | | D41610J | 13 | | | 115-199 |
| 0402 | 22 | GA | | | 3-0 | 29-11-12 | D41620J | 24 | | | D41610J | 1 | | | 115-199 |
| 0434 | 20 | GA | | | 0-18 | 28-41-11 | D41618J | | | FR | GD01888 | ST.. | 2 | | 115-199 |
| 0444 | 20 | GA | | | 4-0 | 32-12-12 | D42018J | 25 | | | TB0182Y | C003 | BJ | | 001-099 |
| 0444 | 20 | GA | | | 3-0 | 32-12-12 | D42018J | 34 | | | TB0182Y | C003 | BJ | | 115-199 |
| 0445 | 20 | GA | | | 4-0 | 32-12-12 | D42018J | 31 | | | D42012J | 20 | | | 001-099 |
| 0445 | 20 | GA | | | 3-0 | 32-12-12 | D42018J | 35 | | | D42012J | 20 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 11

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0446 | 20 | | GA | | 4-0 | 32-12-12 | | D42012J | 22 | | | TB0182Y | C003 | BJ | | 001-099 |
| 0446 | 20 | | GA | | 3-0 | 32-12-12 | | TB0182Y | C003 | BJ | | D42012J | 21 | | | 115-199 |
| 0447 | 20 | | GA | | 4-0 | 32-35-11 | | D42012J | 17 | | | TB0182Y | C003 | BJ | | 001-099 |
| 0447 | 20 | | GA | | 3-0 | 32-35-11 | | TB0182Y | C003 | BJ | | D42012J | 17 | | | 115-199 |
| 0448 | 20 | | GA | | 4-0 | 32-35-11 | | D42012J | 19 | | | TB0182Y | C003 | BJ | | 001-099 |
| 0448 | 20 | | GA | | 3-0 | 32-35-11 | | TB0182Y | C003 | BJ | | D42012J | 19 | | | 115-199 |
| 0449 | 22 | | GA | | 4-0 | 32-61-21 | | D42016J | 31 | | | TB0182Y | C018 | BJ | | 001-099 |
| 0449 | 22 | | GA | | 3-0 | 32-61-21 | | D42016J | 31 | | | TB0182Y | C018 | BJ | | 115-199 |
| 0450 | 22 | | GA | | 3-0 | 32-61-21 | | D41876J | 2 | | | TB0182Y | C018 | BJ | | 001-099 |
| 0450 | 22 | | GA | | 4-0 | 32-61-21 | | D41876J | 2 | | | TB0182Y | C018 | BJ | | 115-199 |
| 0451 | 16 | | GA | | 4-0 | 75-31-11 | | D42014J | 16 | 16 | | TB0182A | C022 | 2 | | 001-099 |
| 0451 | 16 | | GA | | 3-0 | 75-31-11 | | D42014J | 16 | 16 | | TB0182A | C022 | 2 | | 115-199 |
| 0452 | 16 | | GA | | 4-0 | 75-31-11 | | D42014J | 17 | 16 | | TB0182A | C022 | 2 | | 001-099 |
| 0452 | 16 | | GA | | 3-0 | 75-31-11 | | D42014J | 17 | 16 | | TB0182A | C022 | 2 | | 115-199 |
| 0453 | 16 | | GA | | 2-0 | 75-31-11 | | GD01883 | DC.. | 2 | | TB0182A | A022 | 2 | | 001-099 |
| 0453 | 16 | | GA | | 3-0 | 75-31-11 | | GD01883 | DC.. | 2 | | TB0182A | A022 | 2 | | 115-199 |
| 0454 | 20 | | GA | | 5-0 | 32-35-11 | | D42169J | 1 | | | D42016J | 27 | | | 115-199 |
| 0455 | 24 | | GK | | 3-0 | 29-33-11 | | D02598A | B04 | | | D42016J | 47 | | | 001-099 |
| 0456 | 24 | | GK | | 3-0 | 29-33-11 | | D02598A | C04 | | | D42016J | 48 | | | 001-099 |
| 0457 | 24 | | GK | | 3-0 | 29-33-11 | | D02598A | A04 | | | D42016J | 49 | | | 001-099 |
| 0458 | 22 | | GA | | 3-0 | 29-33-11 | | D02598A | B08 | | | GD01883 | AC.. | 2 | | 001-099 |
| 0459 | 24 | | GK | | 3-0 | 29-33-11 | | D02598A | B13 | | | D42016J | 44 | | | 001-099 |
| 0460 | 22 | | GA | | 3-0 | 29-33-11 | | D02598A | C13 | | | D42016J | 45 | | | 001-099 |
| 0461 | 24 | | GK | | 3-0 | 29-33-11 | | D02598A | A13 | | | D42016J | 46 | | | 001-099 |
| 0462 | 24 | | GK | | 3-0 | 29-33-11 | | D02598B | B07 | | | D42018J | 38 | | | 001-099 |
| 0463 | 24 | | GK | | 3-0 | 29-33-11 | | D02598B | C07 | | | D42018J | 39 | | | 001-099 |
| 0464 | 24 | | GK | | 3-0 | 29-33-11 | | D02598B | A07 | | | D42018J | 40 | | | 001-099 |
| 0465 | 24 | | GK | | 3-0 | 29-33-11 | | D02598B | A14 | | | D42018J | 41 | | | 001-099 |
| 0466 | 24 | | GK | | 4-0 | 29-33-11 | | D02598B | A15 | | | GD01888 | ST.. | 2 | | 001-099 |
| 0467 | 22 | | GA | | 3-0 | 29-33-11 | | D02598B | A12 | | | GD01882 | DC.. | 2 | | 001-099 |
| 0468 | 22 | | GA | | 3-0 | 29-33-11 | | D02598B | A13 | | | GD01882 | DC.. | 2 | | 001-099 |
| 0469 | 22 | | GA | | 3-0 | 29-33-11 | | D02598B | B01 | | | GD01883 | AC.. | 2 | | 001-099 |
| 0470 | 22 | | GA | | 3-0 | 29-33-11 | | D02598B | B11 | | | GD01883 | AC.. | 2 | | 001-099 |
| 0471 | 24 | | GK | | 3-0 | 29-33-11 | | D02598B | C08 | | | D42018J | 42 | | | 001-099 |
| 0472 | 24 | | GK | | 3-0 | 29-33-11 | | D02598A | C14 | | | D42018J | 43 | | | 001-099 |
| 0473 | 24 | | GK | | 3-0 | 29-33-11 | | D02598A | C05 | | | D42018J | 44 | | | 001-099 |
| 0474 | 22 | | GA | | 4-0 | 29-33-11 | | D02598A | A08 | | | D40702J | 10 | | | 001-099 |
| 0475 | 22 | | GA | | 4-0 | 29-33-11 | | D02598B | A01 | | | D40702J | 11 | | | 001-099 |
| 0476 | 22 | | GA | | 4-0 | 29-33-11 | | D02598B | A11 | | | D40702J | 12 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 12

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------------------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | | | | | | | | | | | | | | | |
| | | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | |
| 0477 | 24 | GK | | | 3-0 | 29-33-11 | D02598A | A14 | | | D42016J | 41 | | | 001-099 |
| 0478 | 24 | GK | | | 3-0 | 29-33-11 | D02598A | A05 | | | D42016J | 42 | | | 001-099 |
| 0479 | 24 | GK | | | 3-0 | 29-33-11 | D02598B | A08 | | | D42016J | 43 | | | 001-099 |
| 0480 | 24 | GK | | | 3-0 | 29-33-11 | D02598A | A06 | | | D41610J | 44 | | | 001-099 |
| 0481 | 24 | GK | | | 3-0 | 29-33-11 | D02598B | A09 | | | D41876J | 31 | | | 001-099 |
| 0482 | 24 | GK | | | 3-0 | 29-33-11 | D02598A | A15 | | | D42016J | 53 | | | 001-099 |
| 0490 | 20 | GA | | | 2-0 | 29-21-31 | D42016J | 29 | | | D42018J | 14 | | | 001-099 |
| 0490 | 20 | GA | | | 3-0 | 29-21-31 | D42016J | 29 | | | D42018J | 14 | | | 115-199 |
| 0494 | 24 | GK | | | 4-0 | 31-31-62 | D41445J | 16 | | | D41876J | 4 | | | 001-099 |
| 0499 | 22 | GA | | | 2-0 | 34-45-01 | D41311J | 12 | | | SM00003 | | WI | | 001 |
| 0499 | 22 | GA | | | 2-0 | 34-45-01 | D41311J | 12 | | | SM00003 | | W | | 002 |
| 0499 | 22 | GA | | | 2-0 | 34-45-01 | D41311J | 12 | | | SM00004 | | WI | | 003-099 |
| 0499 | 22 | GA | | | 4-0 | 34-45-01 | D41311J | 12 | | | SM00003 | | WI | | 115-199 |
| 0503 | 24 | GK | | | 3-0 | 32-61-12 | TB0182C | A027 | 2 | | SM00003 | | WI | | 001, 003-099 |
| 0503 | 24 | GK | | | 3-0 | 32-61-12 | TB0182C | A027 | 2 | | SM00003 | | W | | 002 |
| 0503 | 24 | GK | | | 4-0 | 32-61-11 | TB0182C | A027 | 2 | | SM00003 | | WI | | 115-199 |
| 0504 | 24 | GK | | | 3-0 | 32-61-12 | TB0182C | A028 | 2 | | SM00003 | | WI | | 001, 003-099 |
| 0504 | 24 | GK | | | 3-0 | 32-61-12 | TB0182C | A028 | 2 | | SM00003 | | W | | 002 |
| 0504 | 24 | GK | | | 4-0 | 32-61-12 | TB0182C | A028 | 2 | | SM00003 | | WI | | 115-199 |
| 0506 | 24 | GK | | | 3-0 | 28-41-14 | D02440A | H08 | | | D41610J | 31 | | | ALL |
| 0507 | 20 | GA | | | 4-0 | 28-41-11 | D40996J | 9 | | | TB0182Y | C034 | BJ | | ALL |
| 0512 | 22 | GA | | | 4-0 | 28-41-41 | D02440A | H11 | | | GD01883 | DC.. | 2 | | ALL |
| 0513 | 22 | GA | | | 4-0 | 28-21-11 | D02440C | K10 | | | TB0182Y | C034 | BJ | | ALL |
| 0515 | 22 | GA | | | 4-0 | 28-21-11 | D02440C | A10 | | | TB0182Y | A034 | BJ | | ALL |
| 0518 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | C05 | | | D41272J | 6 | | | ALL |
| 0519 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | D05 | | | D41272J | 7 | | | ALL |
| 0520 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | E05 | | | D41272J | 8 | | | ALL |
| 0521 | 24 | GK | | | 3-0 | 28-41-21 | D02440A | D06 | | | D41272J | 9 | | | ALL |
| 0523 | 24 | GK | | | 0-9 | 28-41-21 | D02440C | C02 | | | D02440C | CAP | Y | | 001-099 |
| 0523 | 24 | GK | | | 0-7 | 28-41-21 | D02440C | C02 | | | D02440C | CAP | Y | | 115-199 |
| 0524 | 24 | GK | | | 0-9 | 28-41-21 | D02440C | C01 | | | D02440C | CAP | Y | | 001-099 |
| 0524 | 24 | GK | | | 0-7 | 28-41-21 | D02440C | C01 | | | D02440C | CAP | Y | | 115-199 |
| 0525 | 24 | GK | | | 0-9 | 28-41-21 | D02440C | B03 | | | D02440C | CAP | Y | | 001-099 |
| 0525 | 24 | GK | | | 0-7 | 28-41-21 | D02440C | B03 | | | D02440C | CAP | Y | | 115-199 |
| 0526 | 24 | GK | | | 0-9 | 28-41-21 | D02440C | B01 | | | D02440C | CAP | Y | | 001-099 |
| 0526 | 24 | GK | | | 0-7 | 28-41-21 | D02440C | B01 | | | D02440C | CAP | Y | | 115-199 |
| 0527 | 24 | GK | | | 0-9 | 28-41-21 | D02440C | A03 | | | D02440C | CAP | Y | | 001-099 |
| 0527 | 24 | GK | | | 0-7 | 28-41-21 | D02440C | A03 | | | D02440C | CAP | Y | | 115-199 |
| 0528 | 24 | GK | | | 0-9 | 28-41-21 | D02440C | A02 | | | D02440C | CAP | Y | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 13

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 0528 | 24 | | GK | | 0-7 | 28-41-21 | | D02440C | A02 | | | D02440C | CAP | Y | | 115-199 |
| 0530 | 24 | | GK | | 0-9 | 28-41-31 | | D02440C | J03 | | | D02440C | CAP | Y | | 001-099 |
| 0530 | 24 | | GK | | 0-7 | 28-41-31 | | D02440C | J03 | | | D02440C | CAP | Y | | 115-199 |
| 0531 | 24 | | GK | | 0-9 | 28-41-31 | | D02440C | H03 | | | D02440C | CAP | Y | | 001-099 |
| 0531 | 24 | | GK | | 0-7 | 28-41-31 | | D02440C | H03 | | | D02440C | CAP | Y | | 115-199 |
| 0532 | 24 | | GK | | 0-9 | 28-41-31 | | D02440C | K02 | | | D02440C | CAP | Y | | 001-099 |
| 0532 | 24 | | GK | | 0-7 | 28-41-31 | | D02440C | K02 | | | D02440C | CAP | Y | | 115-199 |
| 0533 | 24 | | GK | | 0-9 | 28-41-31 | | D02440C | H02 | | | D02440C | CAP | Y | | 001-099 |
| 0533 | 24 | | GK | | 0-7 | 28-41-31 | | D02440C | H02 | | | D02440C | CAP | Y | | 115-199 |
| 0534 | 24 | | GK | | 0-9 | 28-41-31 | | D02440C | K01 | | | D02440C | CAP | Y | | 001-099 |
| 0534 | 24 | | GK | | 0-7 | 28-41-31 | | D02440C | K01 | | | D02440C | CAP | Y | | 115-199 |
| 0535 | 24 | | GK | | 0-9 | 28-41-31 | | D02440C | J01 | | | D02440C | CAP | Y | | 001-099 |
| 0535 | 24 | | GK | | 0-7 | 28-41-31 | | D02440C | J01 | | | D02440C | CAP | Y | | 115-199 |
| 0536 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | A05 | | | D41276J | 6 | | | ALL |
| 0537 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | B05 | | | D41276J | 7 | | | ALL |
| 0538 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | C05 | | | D41276J | 8 | | | ALL |
| 0539 | 24 | | GK | | 5-0 | 28-41-31 | | D02440B | D05 | | | D41276J | 9 | | | ALL |
| 0540 | 24 | | GK | | 2-0 | 28-41-14 | | D02440B | C08 | | | SM00013 | | WI | | 001-099 |
| 0540 | 24 | | GK | | 2-0 | 28-41-14 | | D02440B | C08 | | | SM00014 | | WI | | 115-199 |
| 0541 | 24 | | GK | | 2-0 | 28-41-14 | | D02440B | C09 | | | SM00014 | | WI | | ALL |
| 0542 | 24 | | GK | | 2-0 | 28-41-14 | | D02440B | D09 | | | SM00013 | | WI | | ALL |
| 0543 | 24 | | GK | | 2-0 | 28-41-14 | | D02440B | E09 | | | SM00013 | | WI | | ALL |
| 0544 | 24 | | GK | | 2-0 | 28-41-14 | | D02440B | F09 | | | SM00014 | | WI | | ALL |
| 0545 | 24 | | GK | | 2-0 | 28-41-14 | | D02440B | D08 | | | SM00014 | | WI | | ALL |
| 0546 | 24 | | GK | | 2-0 | 28-41-14 | | D02440B | E08 | | | SM00013 | | WI | | ALL |
| 0547 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | F13 | | | SM00015 | | WI | | 001-099 |
| 0547 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | F13 | | | SM00016 | | WI | | 115-199 |
| 0548 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | G13 | | | SM00015 | | WI | | ALL |
| 0549 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | H13 | | | SM00016 | | WI | | ALL |
| 0550 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | J13 | | | SM00015 | | WI | | ALL |
| 0551 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | K13 | | | SM00016 | | WI | | ALL |
| 0552 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | J12 | | | SM00016 | | WI | | ALL |
| 0553 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | K12 | | | SM00015 | | WI | | ALL |
| 0554 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | J01 | | | SM00017 | | WI | | 001-099 |
| 0554 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | J01 | | | SM00018 | | WI | | 115-199 |
| 0555 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | J02 | | | SM00017 | | WI | | ALL |
| 0556 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | J03 | | | SM00017 | | WI | | ALL |
| 0557 | 24 | | GK | | 1-0 | 28-41-14 | | D02440A | J04 | | | SM00017 | | WI | | ALL |
| 0558 | 24 | | GK | | 2-0 | 28-41-14 | | D02440A | K01 | | | D02440A | K02 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 14

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | | | | | | | | | | | | | | | |
| | | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | |
| 0558 | 24 | GK | | | 1-0 | 28-41-14 | D02440A | K01 | | | SM00018 | | WI | | 115-199 |
| 0559 | 24 | GK | | | 1-0 | 28-41-14 | D02440A | K03 | | | SM00017 | | WI | | ALL |
| 0577 | 22 | GA | | | 3-0 | 28-21-22 | D02440C | E09 | | | GD01884 | DC.. | 2 | | 001-099 |
| 0577 | 22 | GA | | | 4-0 | 28-21-22 | D02440C | E09 | | | GD01888 | DC.. | 2 | | 115-199 |
| 0578 | 22 | GA | | | 3-0 | 28-21-22 | D02440C | E02 | | | GD01884 | DC.. | 2 | | 001-099 |
| 0578 | 22 | GA | | | 4-0 | 28-21-22 | D02440C | E02 | | | GD01888 | DC.. | 2 | | 115-199 |
| 0579 | 22 | GA | | | 4-0 | 28-41-31 | D02440B | K04 | | | GD01882 | DC.. | 2 | * | 001-099 |
| 0579 | 22 | GA | | | 4-0 | 28-41-31 | D02440B | K04 | | | GD01882 | DC.. | 2 | | 115-199 |
| 0580 | 24 | GK | | | 5-0 | 28-41-41 | D02440A | G09 | | | D41276J | 16 | | | ALL |
| 0581 | 24 | GK | | | 5-0 | 28-41-41 | D02440A | G10 | | | D41276J | 17 | | | ALL |
| 0582 | 24 | GK | | | 5-0 | 28-41-41 | D02440A | G11 | | | D41276J | 18 | | | ALL |
| 0583 | 24 | GK | | | 5-0 | 28-41-41 | D02440A | G12 | | | D41276J | 19 | | | ALL |
| 0584 | 24 | GK | | | 0-9 | 28-41-41 | D02440C | E07 | | | D02440C | CAP | Y | | 001-099 |
| 0584 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | E07 | | | D02440C | CAP | Y | | 115-199 |
| 0585 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | D07 | | | D02440C | CAP | Y | | ALL |
| 0586 | 24 | GK | | | 0-9 | 28-41-41 | D02440C | F06 | | | D02440C | CAP | Y | | 001-099 |
| 0586 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | F06 | | | D02440C | CAP | Y | | 115-199 |
| 0587 | 24 | GK | | | 0-9 | 28-41-41 | D02440C | D06 | | | D02440C | CAP | Y | | 001-099 |
| 0587 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | D06 | | | D02440C | CAP | Y | | 115-199 |
| 0588 | 24 | GK | | | 0-9 | 28-41-41 | D02440C | F05 | | | D02440C | CAP | Y | | 001-099 |
| 0588 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | F05 | | | D02440C | CAP | Y | | 115-199 |
| 0589 | 24 | GK | | | 0-9 | 28-41-41 | D02440C | E05 | | | D02440C | CAP | Y | | 001-099 |
| 0589 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | E05 | | | D02440C | CAP | Y | | 115-199 |
| 0592 | 22 | GA | | | 4-0 | 28-41-11 | D02440B | B09 | | | GD01882 | ST.. | 2 | *1 | 001-099 |
| 0592 | 22 | GA | | | 4-0 | 28-41-11 | D02440B | B09 | | | GD01882 | ST.. | 2 | | 115-199 |
| 0594 | 24 | GK | | | 1-0 | 28-41-14 | D02440A | K02 | | | SM00018 | | WI | | 115-199 |
| 0595 | 24 | GK | | | 3-0 | 28-21-22 | D41614J | 38 | | | D02440A | H07 | | | 001-099 |
| 0598 | 22 | GA | | | 4-0 | 28-21-11 | D02440C | K09 | | | TB0182Y | C034 | BJ | | ALL |
| 0599 | 22 | GA | | | 4-0 | 28-21-11 | D02440C | A09 | | | TB0182Y | A034 | BJ | | ALL |
| 0600 | 22 | GA | | | 3-0 | 28-21-11 | D02440C | C10 | | | GD01884 | DC.. | 2 | | 001-099 |
| 0600 | 22 | GA | | | 4-0 | 28-21-11 | D02440C | C10 | | | GD01883 | DC.. | 2 | | 115-199 |
| 0601 | 22 | GA | | | 3-0 | 28-21-11 | D02440C | H10 | | | GD01884 | DC.. | 2 | | 001-099 |
| 0601 | 22 | GA | | | 4-0 | 28-21-11 | D02440C | H10 | | | GD01883 | DC.. | 2 | | 115-199 |
| 0605 | 24 | GK | | | 2-0 | 28-41-41 | D02440C | B05 | | | D02440C | CAP | Y | | 001-099 |
| 0605 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | B05 | | | D02440C | CAP | Y | | 115-199 |
| 0606 | 24 | GK | | | 2-0 | 28-41-41 | D02440C | C05 | | | D02440C | CAP | Y | | 001-099 |
| 0606 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | C05 | | | D02440C | CAP | Y | | 115-199 |
| 0607 | 24 | GK | | | 2-0 | 28-41-41 | D02440C | A06 | | | D02440C | CAP | Y | | 001-099 |
| 0607 | 24 | GK | | | 0-7 | 28-41-41 | D02440C | A06 | | | D02440C | CAP | Y | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 15

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1280 | 286N1280 | | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | | |
| 0608 | 24 | | GK | | 2-0 | 28-41-41 | D02440C | | C06 | | | D02440C | CAP | Y | | 001-099 | |
| 0608 | 24 | | GK | | 0-7 | 28-41-41 | D02440C | | C06 | | | D02440C | CAP | Y | | 115-199 | |
| 0609 | 24 | | GK | | 2-0 | 28-41-41 | D02440C | | A07 | | | D02440C | CAP | Y | | 001-099 | |
| 0609 | 24 | | GK | | 0-7 | 28-41-41 | D02440C | | A07 | | | D02440C | CAP | Y | | 115-199 | |
| 0610 | 24 | | GK | | 2-0 | 28-41-41 | D02440C | | B07 | | | D02440C | CAP | Y | | 001-099 | |
| 0610 | 24 | | GK | | 0-7 | 28-41-41 | D02440C | | B07 | | | D02440C | CAP | Y | | 115-199 | |
| 0612 | 22 | | GA | | 3-0 | 32-61-11 | D03210A | | D07 | | | SM00004 | | WI | | 003-099 | |
| 0613 | 20 | | GA | | 0-10 | 28-41-11 | D41614J | | | | FV | GD01888 | ST.. | 2 | | 115-199 | |
| 0614 | 20 | | GA | | 0-10 | 28-41-11 | D40996J | | | | FT | GD01888 | ST.. | 2 | | 115-199 | |
| 0615 | 20 | | GA | | 0-10 | 28-41-11 | D41876J | | | | FS | GD01888 | ST.. | 2 | | 115-199 | |
| 0616 | 20 | | GA | | 0-10 | 28-41-11 | D41614J | | | | FU | GD01888 | ST.. | 2 | | 115-199 | |
| 0643 | 22 | | GA | | 2-11 | 27-11-11 | D40996J | | 1 | | | SM00005 | | WI | | 010-099 | |
| 0644 | 22 | | GA | | 2-11 | 27-11-11 | D40996J | | 2 | | | SM00006 | | WI | | 010-099 | |
| 0646 | 22 | | GA | | 2-1 | 31-31-61 | D41311J | | 23 | | | SM00005 | | WI | | 010-099 | |
| 0647 | 22 | | GA | | 2-1 | 31-31-61 | D41311J | | 24 | | | SM00006 | | WI | | 010-099 | |
| 0688 | 22 | | GA | | 1-10 | 34-43-14 | D41445J | | 31 | | | SM00003 | | W | | 002 | |
| 0691 | 22 | | GA | | 3-0 | 31-31-61 | D03210D | | K12 | | | D41445J | | 17 | | 010-099 | |
| 0692 | 22 | | GA | | 3-0 | 31-31-61 | D03210D | | J12 | | | D41445J | | 18 | | 010-099 | |
| 0693 | 22 | | GA | | 3-0 | 31-31-61 | D03210A | | C12 | | | D41445J | | 19 | | 010-099 | |
| 0694 | 22 | | GA | | 3-0 | 31-31-61 | D03210A | | B12 | | | D41445J | | 20 | | 010-099 | |
| 0695 | 22 | | GA | | 2-11 | 31-31-61 | D03210B | | H13 | | | D41445J | | 21 | | 010-099 | |
| 0696 | 22 | | GA | | 2-11 | 31-31-61 | D03210B | | J13 | | | D41445J | | 22 | | 010-099 | |
| 0697 | 22 | | GA | | 2-11 | 31-31-61 | D03210E | | B12 | | | D41445J | | 23 | | 010-099 | |
| 0698 | 22 | | GA | | 2-11 | 31-31-61 | D03210E | | C12 | | | D41445J | | 31 | | 010-099 | |
| 1001 | 22 | | GT | HA | 5-0 | 28-41-21 | D02440C | | B02 | | | D42220J | | 1 | | 001-099 | |
| 1001 | 22 | | GT | HA | 4-0 | 28-41-21 | D02440C | | B02 | | | D42220J | | 1 | VN | 115-199 | |
| 1001Z | | | | HA | 0-0 | 28-41-21 | D02440C | | | | FZ | D42220J | = C1 | | | ALL | |
| 1002 | 22 | | GT | HB | 5-0 | 28-41-31 | D02440C | | J02 | | | D42222J | | 1 | | 001-099 | |
| 1002 | 22 | | GT | HB | 5-0 | 28-41-31 | D02440C | | J02 | | | D42222J | | 1 | VN | 115-199 | |
| 1002Z | | | | HB | 0-0 | 28-41-31 | D02440C | | | | FY | D42222J | = C1 | | | ALL | |
| 1003 | 22 | | GT | HC | 5-0 | 28-41-41 | D02440C | | E06 | | | D42226J | | 1 | | 001-099 | |
| 1003 | 22 | | GT | HC | 5-0 | 28-41-41 | D02440C | | E06 | | | D42226J | | 1 | VN | 115-199 | |
| 1003Z | | | | HC | 0-0 | 28-41-41 | D02440C | | | | FX | D42226J | = C1 | | | ALL | |
| 1004 | 22 | | GT | HD | 5-0 | 28-41-41 | D02440A | | J09 | | | D41276J | | 11 | | ALL | |
| 1004Z | | | | HD | 0-0 | 28-41-41 | D02440A | | K10 | | | D41276J | | 14 | | ALL | |
| 1005 | 24 | | G1 | DX | 4-0 | 29-33-11 | D42138J | | 1 | | | D02598A | B02 | | | 001-099 | |
| 1005Z | | | | DX | 0-0 | 29-33-11 | D42138J | | = C1 | | | D02598A | C02 | | | 001-099 | |
| 1006 | 24 | | G1 | DY | 4-0 | 29-33-11 | D42132J | | 1 | | | D02598A | B11 | | | 001-099 | |
| 1006Z | | | | DY | 0-0 | 29-33-11 | D42132J | | = C1 | | | D02598A | C10 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 16

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 1007 | 24 | G1 | DZ | | 4-0 | 29-33-11 | D42134J | | 1 | | D02598B | B05 | | | 001-099 |
| 1007Z | | | DZ | | 0-0 | 29-33-11 | D42134J | | = C1 | | D02598B | C04 | | | 001-099 |
| 1008 | 22 | GT | CP | | 3-0 | 28-41-21 | D02440A | | B06 | | D41272J | 1 | | | 001-099 |
| 1008 | 22 | GT | DL | | 3-0 | 28-41-21 | D02440A | | B06 | | D41272J | 1 | | | 115-199 |
| 1008Z | | | CP | | 0-0 | 28-41-21 | D02440A | | A06 | | D41272J | 4 | | | 001-099 |
| 1008Z | | | DL | | 0-0 | 28-41-21 | D02440A | | A06 | | D41272J | 4 | | | 115-199 |
| 1009 | 22 | GT | HE | | 5-0 | 28-41-41 | D02440C | | B06 | | D42224J | 1 | | | 001-099 |
| 1009 | 22 | GT | HE | | 5-0 | 28-41-41 | D02440C | | B06 | | D42224J | 1 | VN | | 115-199 |
| 1009Z | | | HE | | 0-0 | 28-41-41 | D02440C | | | FW | D42224J | = C1 | | | ALL |
| 1011 | 22 | GT | CO | | 5-0 | 28-41-31 | D02440B | | D07 | | D41276J | 1 | | | 001-099 |
| 1011 | 22 | GT | DD | | 5-0 | 28-41-31 | D02440B | | D07 | | D41276J | 1 | | | 115-199 |
| 1011Z | | | CO | | 0-0 | 28-41-31 | D02440B | | E06 | | D41276J | 4 | | | 001-099 |
| 1011Z | | | DD | | 0-0 | 28-41-31 | D02440B | | E06 | | D41276J | 4 | | | 115-199 |
| 2001B | 22 | GB | AA | | 3-0 | 52-34-11 | D03210D | | A01 | | D41928J | 4 | | | ALL |
| 2001R | 22 | GB | AA | | 0-0 | 52-34-11 | D03210D | | B01 | | D41928J | 5 | | | ALL |
| 2002B | 24 | GL | AB | | 3-0 | 52-71-21 | D03210B | | F03 | | D41930J | 6 | | | 115-199 |
| 2002R | 24 | GL | AB | | 0-0 | 52-71-21 | D03210B | | E03 | | D41930J | 5 | | | 115-199 |
| 2003B | 22 | GB | AC | | 3-0 | 52-34-11 | D03210D | | F01 | | D41928J | 9 | | | ALL |
| 2003R | 22 | GB | AC | | 0-0 | 52-34-11 | D03210D | | E01 | | D41928J | 8 | | | ALL |
| 2005B | 24 | GL | AE | | 3-0 | 52-35-11 | D03210D | | B05 | | D41930J | 4 | | | ALL |
| 2005R | 24 | GL | AE | | 0-0 | 52-35-11 | D03210D | | A05 | | D41930J | 3 | | | ALL |
| 2007B | 24 | GL | AG | | 3-0 | 52-35-11 | D03210D | | F05 | | D41930J | 8 | | | ALL |
| 2007R | 24 | GL | AG | | 0-0 | 52-35-11 | D03210D | | E05 | | D41930J | 7 | | | ALL |
| 2009B | 24 | GL | AI | | 4-0 | 52-71-11 | D03210B | | D01 | | D41706J | 3 | | | 001-099 |
| 2009B | 24 | GL | AI | | 3-0 | 52-71-11 | D03210B | | D01 | | D41706J | 3 | | | 115-199 |
| 2009R | 24 | GL | AI | | 0-0 | 52-71-11 | D03210B | | C01 | | D41706J | 2 | | | ALL |
| 2010B | 24 | GL | AJ | | 4-0 | 52-71-11 | D03210B | | H02 | | D41706J | 5 | | | 001-099 |
| 2010B | 24 | GL | AJ | | 3-0 | 52-71-11 | D03210B | | H02 | | D41706J | 5 | | | 115-199 |
| 2010R | 24 | GL | AJ | | 0-0 | 52-71-11 | D03210B | | G02 | | D41706J | 4 | | | ALL |
| 2011B | 24 | GL | AK | | 4-0 | 52-71-11 | D03210B | | F01 | | D41706J | 7 | | | 001-099 |
| 2011B | 24 | GL | AK | | 3-0 | 52-71-11 | D03210B | | F01 | | D41706J | 7 | | | 115-199 |
| 2011R | 24 | GL | AK | | 0-0 | 52-71-11 | D03210B | | E01 | | D41706J | 6 | | | ALL |
| 2012B | 24 | GL | AL | | 4-0 | 52-71-11 | D03210B | | K02 | | D41706J | 9 | | | 001-099 |
| 2012B | 24 | GL | AL | | 3-0 | 52-71-11 | D03210B | | K02 | | D41706J | 9 | | | 115-199 |
| 2012R | 24 | GL | AL | | 0-0 | 52-71-11 | D03210B | | J02 | | D41706J | 8 | | | ALL |
| 2013B | 24 | GL | AM | | 3-0 | 52-71-11 | D03210B | | B03 | | D41706J | 11 | | | 115-199 |
| 2013R | 24 | GL | AM | | 0-0 | 52-71-11 | D03210B | | A03 | | D41706J | 10 | | | 115-199 |
| 2014B | 24 | GL | AN | | 4-0 | 52-71-11 | D03210B | | D03 | | D41706J | 13 | | | 001-099 |
| 2014B | 24 | GL | AN | | 3-0 | 52-71-11 | D03210B | | D03 | | D41706J | 13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 17

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 2014R | 24 | GL | AN | | 0-0 | 52-71-11 | D03210B | | C03 | | D41706J | 12 | | | ALL |
| 2015B | 24 | GL | AO | | 4-0 | 52-71-21 | D03210B | | K01 | | D41708J | 3 | | | ALL |
| 2015R | 24 | GL | AO | | 0-0 | 52-71-21 | D03210B | | J01 | | D41708J | 2 | | | ALL |
| 2016B | 24 | GL | AP | | 4-0 | 52-71-21 | D03210B | | B02 | | D41708J | 5 | | | ALL |
| 2016R | 24 | GL | AP | | 0-0 | 52-71-21 | D03210B | | A02 | | D41708J | 4 | | | ALL |
| 2017B | 24 | GL | AQ | | 4-0 | 52-71-21 | D03210B | | D02 | | D41708J | 7 | | | 115-199 |
| 2017R | 24 | GL | AQ | | 0-0 | 52-71-21 | D03210B | | C02 | | D41708J | 6 | | | 115-199 |
| 2018B | 24 | GL | AR | | 4-0 | 52-71-21 | D03210B | | F02 | | D41708J | 9 | | | ALL |
| 2018R | 24 | GL | AR | | 0-0 | 52-71-21 | D03210B | | E02 | | D41708J | 8 | | | ALL |
| 2019B | 24 | GL | AS | | 3-0 | 52-71-21 | D03210B | | B01 | | D41928J | 13 | | | ALL |
| 2019R | 24 | GL | AS | | 0-0 | 52-71-21 | D03210B | | A01 | | D41928J | 12 | | | ALL |
| 2020B | 24 | GL | AT | | 3-0 | 52-71-21 | D03210B | | H01 | | D41930J | 13 | | | ALL |
| 2020R | 24 | GL | AT | | 0-0 | 52-71-21 | D03210B | | G01 | | D41930J | 12 | | | ALL |
| 2021B | 24 | GL | AU | | 4-0 | 78-36-11 | D03210E | | B09 | | D42016J | 2 | | | ALL |
| 2021R | 24 | GL | AU | | 0-0 | 78-36-11 | D03210E | | A09 | | D42016J | 1 | | | ALL |
| 2022B | 24 | GL | AV | | 4-0 | 78-36-11 | D03210E | | F09 | | D42016J | 6 | | | 001-099 |
| 2022B | 24 | GL | AV | | 4-0 | 78-36-11 | D03210E | | D09 | | D42016J | 4 | | | 115-199 |
| 2022R | 24 | GL | AV | | 0-0 | 78-36-11 | D03210E | | E09 | | D42016J | 5 | | | 001-099 |
| 2022R | 24 | GL | AV | | 0-0 | 78-36-11 | D03210E | | C09 | | D42016J | 3 | | | 115-199 |
| 2023B | 24 | GL | AW | | 4-0 | 78-36-11 | D03210E | | D09 | | D42016J | 4 | | | 001-099 |
| 2023B | 24 | GL | AW | | 4-0 | 78-36-11 | D03210E | | F09 | | D42016J | 6 | | | 115-199 |
| 2023R | 24 | GL | AW | | 0-0 | 78-36-11 | D03210E | | C09 | | D42016J | 3 | | | 001-099 |
| 2023R | 24 | GL | AW | | 0-0 | 78-36-11 | D03210E | | E09 | | D42016J | 5 | | | 115-199 |
| 2024B | 24 | GL | AX | | 4-0 | 78-36-11 | D03210E | | H09 | | D42016J | 8 | | | ALL |
| 2024R | 24 | GL | AX | | 0-0 | 78-36-11 | D03210E | | G09 | | D42016J | 7 | | | ALL |
| 2025B | 24 | GL | AY | | 4-0 | 78-36-21 | D03210A | | B09 | | D42018J | 2 | | | 001-099 |
| 2025B | 24 | GL | AY | | 3-0 | 78-36-21 | D03210A | | B09 | | D42018J | 2 | | | 115-199 |
| 2025R | 24 | GL | AY | | 0-0 | 78-36-21 | D03210A | | A09 | | D42018J | 1 | | | ALL |
| 2026B | 24 | GL | AZ | | 4-0 | 78-36-21 | D03210A | | F09 | | D42018J | 6 | | | 001-099 |
| 2026B | 24 | GL | AZ | | 3-0 | 78-36-21 | D03210A | | D09 | | D42018J | 4 | | | 115-199 |
| 2026R | 24 | GL | AZ | | 0-0 | 78-36-21 | D03210A | | E09 | | D42018J | 5 | | | 001-099 |
| 2026R | 24 | GL | AZ | | 0-0 | 78-36-21 | D03210A | | C09 | | D42018J | 3 | | | 115-199 |
| 2027B | 24 | GL | BA | | 4-0 | 78-36-21 | D03210A | | D09 | | D42018J | 4 | | | 001-099 |
| 2027B | 24 | GL | BA | | 3-0 | 78-36-21 | D03210A | | F09 | | D42018J | 6 | | | 115-199 |
| 2027R | 24 | GL | BA | | 0-0 | 78-36-21 | D03210A | | C09 | | D42018J | 3 | | | 001-099 |
| 2027R | 24 | GL | BA | | 0-0 | 78-36-21 | D03210A | | E09 | | D42018J | 5 | | | 115-199 |
| 2028B | 24 | GL | BB | | 4-0 | 78-36-21 | D03210A | | H09 | | D42018J | 8 | | | 001-099 |
| 2028B | 24 | GL | BB | | 3-0 | 78-36-21 | D03210A | | H09 | | D42018J | 8 | | | 115-199 |
| 2028R | 24 | GL | BB | | 0-0 | 78-36-21 | D03210A | | G09 | | D42018J | 15 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 18

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|--------------------------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 2028R | 24 | GL | BB | | 0-0 | 78-36-21 | D03210A | G09 | | | D42018J | 7 | | | 115-199 |
| 2029B | 18 | GB | BC | | 3-0 | 28-43-11 | D41876J | 13 | 18 | | D41614J | 26 | 18 | | 001-099 |
| 2029B | 18 | GB | BC | | 3-0 | 28-43-11 | D40996J | 14 | 18 | | D41614J | 26 | 18 | | 115-199 |
| 2029R | 18 | GB | BC | | 0-0 | 28-43-11 | D41876J | 12 | 18 | | D41614J | 27 | 18 | | 001-099 |
| 2029R | 18 | GB | BC | | 0-0 | 28-43-11 | D40996J | 12 | 18 | | D41614J | 27 | 18 | | 115-199 |
| 2037B | 24 | GL | BK | | 4-0 | 32-61-13 | D03210E | B01 | | | D42060J | 14 | | | 001-099 |
| 2037B | 24 | GL | BK | | 3-0 | 32-61-13 | D03210E | B01 | | | D42060J | 14 | | | 115-199 |
| 2037R | 24 | GL | BK | | 0-0 | 32-61-13 | D03210E | A01 | | | D42060J | 15 | | | ALL |
| 2038B | 24 | GL | BL | | 4-0 | 32-61-13 | D03210E | H01 | | | D42060J | 16 | | | 001-099 |
| 2038B | 24 | GL | BL | | 3-0 | 32-61-13 | D03210E | H01 | | | D42060J | 16 | | | 115-199 |
| 2038R | 24 | GL | BL | | 0-0 | 32-61-13 | D03210E | G01 | | | D42060J | 17 | | | ALL |
| 2039B | 24 | GL | BM | | 3-0 | 32-61-13 | D03210E | F03 | | | D41646J | 1 | | | ALL |
| 2039R | 24 | GL | BM | | 0-0 | 32-61-13 | D03210E | E03 | | | D41646J | 2 | | | ALL |
| 2040B | 24 | GL | BN | | 3-0 | 32-61-13 | D03210E | H02 | | | D41646J | 7 | | | ALL |
| 2040R | 24 | GL | BN | | 0-0 | 32-61-13 | D03210E | G02 | | | D41646J | 8 | | | ALL |
| 2041B | 24 | GL | BO | | 3-0 | 32-61-13 | D03210E | F02 | | | D41636J | 6 | | | ALL |
| 2041R | 24 | GL | BO | | 0-0 | 32-61-13 | D03210E | E02 | | | D41636J | 5 | | | ALL |
| 2042B | 24 | GL | BP | | 3-0 | 32-61-13 | D03210E | K01 | | | D41636J | 8 | | | ALL |
| 2042R | 24 | GL | BP | | 0-0 | 32-61-13 | D03210E | J01 | | | D41636J | 7 | | | ALL |
| 2043B | 24 | GL | BQ | | 4-0 | 32-61-22 | D03210E | D01 | | | D42060J | 18 | | | 001-099 |
| 2043B | 24 | GL | BQ | | 3-0 | 32-61-22 | D03210E | D01 | | | D42060J | 18 | | | 115-199 |
| 2043R | 24 | GL | BQ | | 0-0 | 32-61-22 | D03210E | C01 | | | D42060J | 19 | | | ALL |
| 2044B | 24 | GL | BR | | 3-0 | 32-61-22 | D03210E | B02 | | | D41636J | 4 | | | ALL |
| 2044R | 24 | GL | BR | | 0-0 | 32-61-22 | D03210E | A02 | | | D41636J | 3 | | | ALL |
| 2045B | 22 | GB | BS | | 3-0 | 32-61-22 | D03210E | K02 | | | D41646J | 3 | | | ALL |
| 2045R | 22 | GB | BS | | 0-0 | 32-61-22 | D03210E | J02 | | | D41646J | 4 | | | ALL |
| 2046B | 22 | GB | BT | | 3-0 | 32-61-22 | D03210E | B03 | | | D41646J | 5 | | | ALL |
| 2046R | 22 | GB | BT | | 0-0 | 32-61-22 | D03210E | A03 | | | D41646J | 6 | | | ALL |
| 2047B | 24 | GL | BU | | 3-0 | 32-61-22 | D03210A | D01 | | | D41634J | 23 | | | ALL |
| 2047R | 24 | GL | BU | | 0-0 | 32-61-22 | D03210A | C01 | | | D41634J | 21 | | | ALL |
| 2048B | 24 | GL | BW | | 3-0 | 32-61-22 | D03210A | K01 | | | D41610J | 19 | | | ALL |
| 2048R | 24 | GL | BW | | 0-0 | 32-61-22 | D03210A | J01 | | | D41610J | 20 | | | ALL |
| 2049B | 22 | GB | BX | | 4-0 | 32-61-22 | D03210A | H01 | | | D41650J | 4 | | | 001-099 |
| 2049B | 22 | GB | BX | | 3-0 | 32-61-22 | D03210A | H01 | | | D41650J | 4 | | | 115-199 |
| 2049R | 22 | GB | BX | | 0-0 | 32-61-22 | D03210A | G01 | | | D41650J | 3 | | | ALL |
| 2050B | 22 | GB | BY | | 4-0 | 32-61-22 | D03210A | F01 | | | D41650J | 2 | | | 001-099 |
| 2050B | 22 | GB | BY | | 3-0 | 32-61-22 | D03210A | F01 | | | D41650J | 2 | | | 115-199 |
| 2050R | 22 | GB | BY | | 0-0 | 32-61-22 | D03210A | E01 | | | D41650J | 9 | | | ALL |
| 2051B | 22 | GB | BZ | | 3-0 | 78-34-11 | D03210B | D10 | | | D42012J | 4 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 19

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 2051B | 22 | GB | BZ | | 4-0 | 78-34-11 | D03210B | | D10 | | D42012J | | 4 | | 115-199 |
| 2051R | 22 | GB | BZ | | 0-0 | 78-34-11 | D03210B | | C10 | | D42012J | | 3 | | ALL |
| 2052B | 22 | GB | CA | | 3-0 | 78-34-11 | D03210B | | B10 | | D42012J | | 2 | | 001-099 |
| 2052B | 22 | GB | CA | | 4-0 | 78-34-11 | D03210B | | B10 | | D42012J | | 2 | | 115-199 |
| 2052R | 22 | GB | CA | | 0-0 | 78-34-11 | D03210B | | A10 | | D42012J | | 1 | | ALL |
| 2053B | 22 | GB | CB | | 4-0 | 78-34-21 | D03210D | | D10 | | D42014J | | 6 | | 001-099 |
| 2053B | 22 | GB | CB | | 3-0 | 78-34-21 | D03210D | | D10 | | D42014J | | 6 | | 115-199 |
| 2053R | 22 | GB | CB | | 0-0 | 78-34-21 | D03210D | | C10 | | D42014J | | 5 | | ALL |
| 2054B | 22 | GB | CD | | 4-0 | 78-34-21 | D03210D | | B10 | | D42014J | | 4 | | 001-099 |
| 2054B | 22 | GB | CD | | 3-0 | 78-34-21 | D03210D | | B10 | | D42014J | | 4 | | 115-199 |
| 2054R | 22 | GB | CD | | 0-0 | 78-34-21 | D03210D | | A10 | | D42014J | | 3 | | ALL |
| 2057B | 24 | GL | CG | | 3-0 | 28-41-21 | D02440A | | B05 | | D41272J | | 3 | | ALL |
| 2057R | 24 | GL | CG | | 0-0 | 28-41-21 | D02440A | | A05 | | D41272J | | 2 | | ALL |
| 2059B | 24 | GL | CI | | 5-0 | 28-41-41 | D02440A | | J10 | | D41276J | | 13 | | 001-099 |
| 2059B | 24 | GL | CI | | 3-0 | 28-41-41 | D02440A | | J10 | | D41276J | | 13 | | 115-199 |
| 2059R | 24 | GL | CI | | 0-0 | 28-41-41 | D02440A | | H10 | | D41276J | | 12 | | ALL |
| 2063B | 24 | GL | CM | | 5-0 | 28-41-31 | D02440B | | E05 | | D41276J | | 3 | | ALL |
| 2063R | 24 | GL | CM | | 0-0 | 28-41-31 | D02440B | | D06 | | D41276J | | 2 | | ALL |
| 2074B | 24 | GL | CX | | 4-0 | 32-61-13 | D03210A | | F02 | | D41650J | | 10 | | 001-099 |
| 2074B | 24 | GL | CX | | 3-0 | 32-61-13 | D03210A | | F02 | | D41650J | | 10 | | 115-199 |
| 2074R | 24 | GL | CX | | 0-0 | 32-61-13 | D03210A | | E02 | | D41650J | | 11 | | ALL |
| 2075B | 24 | GL | CY | | 4-0 | 32-61-13 | D03210A | | H03 | | D41650J | | 12 | | 001-099 |
| 2075B | 24 | GL | CY | | 3-0 | 32-61-13 | D03210A | | H03 | | D41650J | | 12 | | 115-199 |
| 2075R | 24 | GL | CY | | 0-0 | 32-61-13 | D03210A | | G03 | | D41650J | | 13 | | ALL |
| 2076B | 24 | GL | CZ | | 3-0 | 32-61-13 | D03210A | | B03 | | D41610J | | 25 | | ALL |
| 2076R | 24 | GL | CZ | | 0-0 | 32-61-13 | D03210A | | A03 | | D41610J | | 24 | | ALL |
| 2080B | 24 | GL | KD | | 3-0 | 28-41-14 | D02440B | | E07 | | D40996J | | 17 | | ALL |
| 2080R | 24 | GL | KD | | 0-0 | 28-41-14 | D02440B | | C07 | | D40996J | | 18 | | ALL |
| 2081B | 24 | GL | KE | | 3-0 | 32-61-13 | D03210A | | F03 | | D41610J | | 27 | | ALL |
| 2081R | 24 | GL | KE | | 0-0 | 32-61-13 | D03210A | | E03 | | D41610J | | 26 | | ALL |
| 2084B | 24 | GL | KH | | 3-0 | 32-61-13 | D03210A | | K02 | | D41634J | | 10 | | ALL |
| 2084R | 24 | GL | KH | | 0-0 | 32-61-13 | D03210A | | J02 | | D41634J | | 11 | | ALL |
| 2087B | 24 | GL | KL | | 3-0 | 32-61-13 | D03210A | | D03 | | D41634J | | 12 | | ALL |
| 2087R | 24 | GL | KL | | 0-0 | 32-61-13 | D03210A | | C03 | | D41634J | | 13 | | ALL |
| 2088B | 24 | GL | KM | | 3-0 | 28-21-22 | D02440A | | E06 | | D41614J | | 14 | | 115-199 |
| 2088R | 24 | GL | KM | | 0-0 | 28-21-22 | D02440A | | F08 | | D41614J | | 15 | | 115-199 |
| 2091B | 22 | GB | KP | | 4-0 | 32-09-11 | D03210A | | B01 | | D41650J | | 7 | | 001-099 |
| 2091B | 22 | GB | KP | | 3-0 | 32-09-11 | D03210A | | B01 | | D41650J | | 7 | | 115-199 |
| 2091R | 22 | GB | KP | | 0-0 | 32-09-11 | D03210A | | A01 | | D41650J | | 8 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 20

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--------------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 2092B | 22 | GB | KQ | 3-0 | 32-09-11 | D03210A | B02 | | | | D41634J | 6 | | | ALL |
| 2092R | 22 | GB | KQ | 0-0 | 32-09-11 | D03210A | A02 | | | | D41634J | 7 | | | ALL |
| 2093B | 22 | GB | KR | 3-0 | 32-09-11 | D03210A | D02 | | | | D41610J | 12 | | | ALL |
| 2093R | 22 | GB | KR | 0-0 | 32-09-11 | D03210A | C02 | | | | D41610J | 11 | | | ALL |
| 2094B | 22 | GB | KS | 3-0 | 32-09-12 | D03210E | D03 | | | | D41646J | 9 | | | ALL |
| 2094R | 22 | GB | KS | 0-0 | 32-09-12 | D03210E | C03 | | | | D41646J | 10 | | | ALL |
| 2095B | 22 | GB | KT | 3-0 | 32-09-12 | D03210E | F01 | | | | D41614J | 53 | | | ALL |
| 2095R | 22 | GB | KT | 0-0 | 32-09-12 | D03210E | E01 | | | | D41614J | 54 | | | ALL |
| 2096B | 22 | GB | KU | 3-0 | 32-09-12 | D03210E | D02 | | | | D41636J | 1 | | | ALL |
| 2096R | 22 | GB | KU | 0-0 | 32-09-12 | D03210E | C02 | | | | D41636J | 2 | | | ALL |
| 2099B | 24 | GL | KX | 3-0 | 28-41-13 | D40996J | 27 | | | | D02440A | K14 | | | 001-099 |
| 2099B | 22 | GB | KX | 4-0 | 28-41-13 | D40996J | 27 | | | | D02440A | K14 | | | 115-199 |
| 2099R | 24 | GL | KX | 0-0 | 28-41-13 | D40996J | 28 | | | | D02440A | A14 | | | 001-099 |
| 2099R | 22 | GB | KX | 0-0 | 28-41-13 | D40996J | 28 | | | | D02440A | A14 | | | 115-199 |
| 2100B | 24 | GL | BI | 4-0 | 52-71-11 | D03210B | B03 | | | | D41706J | 11 | | | 001-099 |
| 2100R | 24 | GL | BI | 0-0 | 52-71-11 | D03210B | A03 | | | | D41706J | 10 | | | 001-099 |
| 2104B | 24 | GL | CE | 4-0 | 52-71-21 | D03210B | D02 | | | | D41708J | 7 | | | 001-099 |
| 2104R | 24 | GL | CE | 0-0 | 52-71-21 | D03210B | C02 | | | | D41708J | 6 | | | 001-099 |
| 2108B | 24 | GL | CL | 3-0 | 28-21-22 | D02440A | E06 | | | | D41614J | 32 | | | 001-099 |
| 2108R | 24 | GL | CL | 0-0 | 28-21-22 | D02440A | F08 | | | | D41614J | 50 | | | 001-099 |
| 2501B | 22 | GU | DF | 2-0 | 28-21-21 | D41610J | 22 | | | | D41876J | 20 | | | 001-099 |
| 2501B | 22 | GU | DF | 3-0 | 28-21-21 | D41610J | 22 | | | | D41876J | 20 | | | 115-199 |
| 2501R | 22 | GU | DF | 0-0 | 28-21-21 | D41610J | 21 | | | | D41876J | 19 | | | ALL |
| 2501Z | | | DF | 0-0 | 28-21-21 | D41610J | 23 | | | | D41876J | 21 | | | ALL |
| 2502B | 22 | GU | DG | 3-0 | 28-21-21 | D41634J | 1 | | | | D41876J | 23 | | | 001-099 |
| 2502B | 22 | GU | DG | 4-0 | 28-21-21 | D41634J | 1 | | | | D41876J | 23 | | | 115-199 |
| 2502R | 22 | GU | DG | 0-0 | 28-21-21 | D41634J | 2 | | | | D41876J | 22 | | | ALL |
| 2502Z | | | DG | 0-0 | 28-21-21 | D41634J | 3 | | | | D41876J | 24 | | | ALL |
| 2503B | 22 | GU | AF | 4-0 | 31-31-63 | D41363J | 24 | | | | D42014J | 20 | | | 001-099 |
| 2503R | 22 | GU | AF | 0-0 | 31-31-63 | D41363J | 19 | | | | D42014J | 14 | | | 001-099 |
| 2503Z | | | AF | 0-0 | 31-31-63 | D41363J | 5 | | | | D42014J | 7 | | | 001-099 |
| 2505B | 24 | G2 | BF | 3-0 | 23-41-11 | D42060J | 20 | | | | TB0182Y | C001 | BJ | | 001-099 |
| 2505R | 24 | G2 | BF | 0-0 | 23-41-11 | D42060J | 21 | | | | TB0182Y | A002 | BJ | | 001-099 |
| 2505Z | | | BF | 0-0 | 23-41-11 | D42060J | 23 | | | | TB0182Y | A001 | BJ | | 001-099 |
| 2506B | 24 | G2 | BG | 4-0 | 23-41-11 | D41363J | 14 | | | | TB0182Y | C001 | BJ | | 001-099 |
| 2506R | 24 | G2 | BG | 0-0 | 23-41-11 | D41363J | 15 | | | | TB0182Y | A002 | BJ | | 001-099 |
| 2506Z | | | BG | 0-0 | 23-41-11 | D41363J | 17 | | | | TB0182Y | A001 | BJ | | 001-099 |
| 2507B | 24 | G2 | BH | 3-0 | 23-41-11 | D41634J | 8 | | | | TB0182Y | C001 | BJ | | 001-099 |
| 2507R | 24 | G2 | BH | 0-0 | 23-41-11 | D41634J | 9 | | | | TB0182Y | A002 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 21

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | |
| 2507Z | | | | BH | 0-0 | 23-41-11 | D41634J | 16 | | | TB0182Y | A001 | BJ | | 001-099 |
| 2508B | 22 | GU | KF | | 3-0 | 28-41-11 | D02440A | H05 | | | D41614J | 6 | | | 001-099 |
| 2508B | 24 | G2 | EA | | 3-0 | 28-41-11 | D02440A | H05 | | | D41614J | 6 | | | 115-199 |
| 2508R | 22 | GU | KF | | 0-0 | 28-41-11 | D02440A | G05 | | | D41614J | 7 | | | 001-099 |
| 2508R | 24 | G2 | EA | | 0-0 | 28-41-11 | D02440A | G05 | | | D41614J | 7 | | | 115-199 |
| 2508Z | | | KF | | 0-0 | 28-41-11 | D02440A | DED | | | D41614J | | | FV | 001-099 |
| 2508Z | | | EA | | 0-0 | 28-41-11 | D02440A | DED | | | D41614J | | | FV | 115-199 |
| 2509B | 22 | GU | KJ | | 3-0 | 28-41-11 | D02440B | H05 | | | D41614J | 10 | | | 001-099 |
| 2509B | 22 | GU | JK | | 3-0 | 28-41-11 | D02440B | H05 | | | D41614J | 10 | | | 115-199 |
| 2509R | 22 | GU | KJ | | 0-0 | 28-41-11 | D02440B | G05 | | | D41614J | 11 | | | 001-099 |
| 2509R | 22 | GU | JK | | 0-0 | 28-41-11 | D02440B | G05 | | | D41614J | 11 | | | 115-199 |
| 2509Z | | | KJ | | 0-0 | 28-41-11 | D02440B | DED | | | D41614J | | | FU | 001-099 |
| 2509Z | | | JK | | 0-0 | 28-41-11 | D02440B | DED | | | D41614J | | | FU | 115-199 |
| 2569B | 22 | GU | CS | | 3-0 | 28-41-11 | D02440A | H03 | | | D41876J | 15 | | | 001-099 |
| 2569B | 24 | G2 | BV | | 3-0 | 28-41-11 | D02440A | H03 | | | D41876J | 15 | | | 115-199 |
| 2569R | 22 | GU | CS | | 0-0 | 28-41-11 | D02440A | G03 | | | D41876J | 14 | | | 001-099 |
| 2569R | 24 | G2 | BV | | 0-0 | 28-41-11 | D02440A | G03 | | | D41876J | 14 | | | 115-199 |
| 2569Z | | | CS | | 0-0 | 28-41-11 | D02440A | DED | | | D41876J | | | FS | 001-099 |
| 2569Z | | | BV | | 0-0 | 28-41-11 | D02440A | DED | | | D41876J | | | FS | 115-199 |
| 2572B | 22 | GU | CV | | 3-0 | 28-41-11 | D02440B | H03 | | | D40996J | 23 | | | 001-099 |
| 2572B | 22 | GU | CK | | 4-0 | 28-41-11 | D02440B | H03 | | | D40996J | 23 | | | 115-199 |
| 2572R | 22 | GU | CV | | 0-0 | 28-41-11 | D02440B | G03 | | | D40996J | 22 | | | 001-099 |
| 2572R | 22 | GU | CK | | 0-0 | 28-41-11 | D02440B | G03 | | | D40996J | 22 | | | 115-199 |
| 2572Z | | | CV | | 0-0 | 28-41-11 | D02440B | DED | | | D40996J | | | FT | 001-099 |
| 2572Z | | | CK | | 0-0 | 28-41-11 | D02440B | DED | | | D40996J | | | FT | 115-199 |
| 3001B | 24 | GM | DA | | 3-0 | 28-21-22 | D41614J | 41 | | | SM00001 | | WI | | 001-099 |
| 3001B | 24 | GM | DA | | 3-0 | 28-21-22 | D41614J | 41 | | | SM00001 | | 9 | | 115-199 |
| 3001R | 24 | GM | DA | | 0-0 | 28-21-22 | D41614J | 42 | | | D02440A | C07 | | | ALL |
| 3001Y | 24 | GM | DA | | 0-0 | 28-21-22 | D41614J | 43 | | | D02440A | C06 | | | ALL |
| 3010B | 24 | GM | KV | | 4-0 | 28-41-14 | D02440B | K08 | | | D41620J | 18 | | | 001-099 |
| 3010B | 24 | GM | DM | | 4-0 | 28-41-14 | D02440B | K08 | | | D41620J | 18 | | | 115-199 |
| 3010R | 24 | GM | KV | | 0-0 | 28-41-14 | D02440B | K07 | | | D41620J | 19 | | | 001-099 |
| 3010R | 24 | GM | DM | | 0-0 | 28-41-14 | D02440B | K07 | | | D41620J | 19 | | | 115-199 |
| 3010Y | 24 | GM | KV | | 0-0 | 28-41-14 | D02440B | K06 | | | D41620J | 30 | | | 001-099 |
| 3010Y | 24 | GM | DM | | 0-0 | 28-41-14 | D02440B | K06 | | | D41620J | 30 | | | 115-199 |
| 3011B | 24 | GM | EM | | 3-0 | 28-21-22 | D02440A | F07 | | | D41614J | 31 | | | 001-099 |
| 3011R | 24 | GM | EM | | 0-0 | 28-21-22 | D02440A | F06 | | | D41614J | 30 | | | 001-099 |
| 3011Y | 24 | GM | EM | | 0-0 | 28-21-22 | D02440A | E07 | | | D41614J | 33 | | | 001-099 |
| 3012B | 24 | GM | KW | | 3-0 | 28-41-14 | D02440A | K08 | | | D41876J | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 22

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|--------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1280 | 286N1280 | | | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | | |
| 3012R | 24 | | GM | KW | 0-0 | 28-41-14 | D02440A | K07 | | | | D41876J | 7 | | | ALL |
| 3012Y | 24 | | GM | KW | 0-0 | 28-41-14 | D02440A | K06 | | | | D41876J | 8 | | | ALL |
| 3013B | 24 | | GM | DH | 3-0 | 28-21-22 | D41614J | 55 | | | | D02440B | H07 | | | 001-099 |
| 3013R | 24 | | GM | DH | 0-0 | 28-21-22 | D41614J | 39 | | | | D02440A | F09 | | | 001-099 |
| 3013Y | 24 | | GM | DH | 0-0 | 28-21-22 | D41614J | 40 | | | | SM00001 | | WI | | 001-099 |
| 3501B | 24 | | G3 | NA | 3-0 | 23-41-11 | D42060J | 20 | | | | TB0182Y | C001 | BJ | | 115-199 |
| 3501R | 24 | | G3 | NA | 0-0 | 23-41-11 | D42060J | 21 | | | | TB0182Y | A002 | BJ | | 115-199 |
| 3501Y | 24 | | G3 | NA | 0-0 | 23-41-11 | D42060J | 22 | | | | TB0182Y | C002 | BJ | | 115-199 |
| 3501Z | | | | NA | 0-0 | 23-41-11 | D42060J | 23 | | | | TB0182Y | A001 | BJ | | 115-199 |
| 3502B | 24 | | G3 | NB | 4-0 | 23-41-11 | D41634J | 28 | | | | TB0182Y | C001 | BJ | | 115-199 |
| 3502R | 24 | | G3 | NB | 0-0 | 23-41-11 | D41634J | 29 | | | | TB0182Y | A002 | BJ | | 115-199 |
| 3502Y | 24 | | G3 | NB | 0-0 | 23-41-11 | D41634J | 30 | | | | TB0182Y | C002 | BJ | | 115-199 |
| 3502Z | | | | NB | 0-0 | 23-41-11 | D41634J | 31 | | | | TB0182Y | A001 | BJ | | 115-199 |
| 3503B | 24 | | G3 | NC | 3-0 | 23-41-11 | D41363J | 14 | | | | TB0182Y | C001 | BJ | | 115-199 |
| 3503R | 24 | | G3 | NC | 0-0 | 23-41-11 | D41363J | 15 | | | | TB0182Y | A002 | BJ | | 115-199 |
| 3503Y | 24 | | G3 | NC | 0-0 | 23-41-11 | D41363J | 16 | | | | TB0182Y | C002 | BJ | | 115-199 |
| 3503Z | | | | NC | 0-0 | 23-41-11 | D41363J | 17 | | | | TB0182Y | A001 | BJ | | 115-199 |
| 4001B | 24 | | GN | DB | 3-0 | 28-21-22 | D41614J | 55 | | | | D02440B | H07 | | | 115-199 |
| 4001G | 24 | | GN | DB | 0-0 | 28-21-22 | D41614J | 38 | | | | D02440A | H07 | | | 115-199 |
| 4001R | 24 | | GN | DB | 0-0 | 28-21-22 | D41614J | 39 | | | | D02440A | F09 | | | 115-199 |
| 4001Y | 24 | | GN | DB | 0-0 | 28-21-22 | D41614J | 40 | | | | SM00001 | | 9 | | 115-199 |
| 4006B | 24 | | GN | EM | 3-0 | 28-21-22 | D02440A | F07 | | | | D41614J | 31 | | | 115-199 |
| 4006G | 24 | | GN | EM | 0-0 | 28-21-22 | D02440A | CAP | Y | | | D41614J | CAP | Y | | 115-199 |
| 4006R | 24 | | GN | EM | 0-0 | 28-21-22 | D02440A | F06 | | | | D41614J | 30 | | | 115-199 |
| 4006Y | 24 | | GN | EM | 0-0 | 28-21-22 | D02440A | E07 | | | | D41614J | 33 | | | 115-199 |
| 5001B | 24 | | G2 | FJ | 4-0 | 34-61-24 | D02440B | B06 | | | | D41363J | 12 | | | ALL |
| 5001R | 24 | | G2 | FJ | 0-0 | 34-61-24 | D02440B | A06 | | | | D41363J | 11 | | | ALL |
| 5001Z | | | | FJ | 0-0 | 34-61-24 | D02440B | DED | | | | D41363J | | | AA | ALL |
| 5002B | 24 | | G2 | FI | 4-0 | 34-61-14 | D02440A | K11 | | | | D41311J | 14 | | | 001-009 |
| 5002B | 24 | | G2 | FI | 4-0 | 34-61-14 | D02440A | K11 | | | | TB0182Y | C011 | BJ | | 010-099 |
| 5002B | 24 | | G2 | FI | 3-0 | 34-61-14 | D02440A | K11 | | | | D41311J | 14 | | | 115-199 |
| 5002R | 24 | | G2 | FI | 0-0 | 34-61-14 | D02440A | J11 | | | | D41311J | 13 | | | 001-009, 115-199 |
| 5002R | 24 | | G2 | FI | 0-0 | 34-61-14 | D02440A | J11 | | | | TB0182Y | A011 | BJ | | 010-099 |
| 5002Z | | | | FI | 0-0 | 34-61-14 | D02440A | DED | | | | D41311J | | | AB | 001-009, 115-199 |
| 5002Z | | | | FI | 0-0 | 34-61-14 | D02440A | DED | | | | GD01884 | ST.. | 2 | | 010-099 |
| 5003B | 20 | | GU | AB | 4-0 | 31-31-44 | D41311J | 28 | | | | D42012J | 12 | | | 001-099 |
| 5003B | 24 | | G2 | FK | 4-0 | 31-31-23 | D41311J | 28 | | | | D42012J | 12 | | | 115-199 |
| 5003R | 20 | | GU | AB | 0-0 | 31-31-44 | D41311J | 27 | | | | D42012J | 23 | | | 001-099 |
| 5003R | 24 | | G2 | FK | 0-0 | 31-31-23 | D41311J | 27 | | | | D42012J | 11 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 23

May 17/2006



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | | | | | |
|--------------|-----------------|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|--|--|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | | |
| W1280 | 286N1280 | E3-4 SHELF HARNESS (continued) | | | | | | | | | | | | | | | | | |
| FRVA | | | 0-0 | 28-41-11 | D41614J | | | FV | D41614J | 5 | | | 115-199 | | | | | | |
| FRVB | | | 0-0 | 28-41-11 | D41614J | | | FV | D41614J | 5 | | | 001-099 | | | | | | |
| FRWA | | | 0-0 | 28-41-41 | D02440C | | | FW | D02440C | C07 | | | ALL | | | | | | |
| FRWB | | | 0-0 | 28-41-41 | D02440C | A05 | | | D02440C | | | FW | ALL | | | | | | |
| FRXA | | | 0-0 | 28-41-41 | D02440C | | | FX | D02440C | F07 | | | ALL | | | | | | |
| FRXB | | | 0-0 | 28-41-41 | D02440C | D05 | | | D02440C | | | FX | 001-099 | | | | | | |
| FRXB | | | 0-0 | 28-41-41 | D02440C | | | FX | D02440C | D05 | | | 115-199 | | | | | | |
| FRYA | | | 0-0 | 28-41-31 | D02440C | H01 | | | D02440C | | | FY | ALL | | | | | | |
| FRYB | | | 0-0 | 28-41-31 | D02440C | | | FY | D02440C | K03 | | | ALL | | | | | | |
| FRZA | | | 0-0 | 28-41-21 | D02440C | | | FZ | D02440C | A01 | | | 001-099 | | | | | | |
| FRZB | | | 0-0 | 28-41-21 | D02440C | C03 | | | D02440C | | | FZ | ALL | | | | | | |
| W1282 | 286N1282 | E5-1 SHELF | | | | | | | | | | | | | | | | | |
| 0001 | 22 | GA | 4-2 | 34-33-11 | D00211C | 8 | | | D41882J | 1 | | | ALL | | | | | | |
| 0002 | 20 | GA | 3-1 | 34-33-11 | D00211C | 2 | | | GD02065 | ST.. | 2 | | ALL | | | | | | |
| 0003 | 20 | GA | 3-1 | 34-33-11 | D00211C | 3 | | | GD02065 | AC.. | 2 | | ALL | | | | | | |
| 0004 | 24 | GK | 0-7 | 34-33-11 | D00211B | J06 | | | D00211B | J04 | | | ALL | | | | | | |
| 0005 | 24 | GK | 0-7 | 34-33-11 | D00211B | F02 | | | D00211B | F03 | | | ALL | | | | | | |
| 0006 | 24 | GK | 0-7 | 34-33-11 | D00211B | C05 | | | D00211B | B05 | | | ALL | | | | | | |
| 0007 | 24 | GK | 3-0 | 34-33-11 | D00211B | G05 | | | D41864J | 24 | | | ALL | | | | | | |
| 0008 | 24 | GK | 4-3 | 34-33-11 | D00211B | F04 | | | D41325J | 40 | | | ALL | | | | | | |
| 0009 | 22 | GA | 3-3 | 34-33-11 | D00211B | F06 | | | GD02065 | DC.. | 2 | | 001-099 | | | | | | |
| 0009 | 24 | GK | 3-3 | 34-33-11 | D00211B | F06 | | | GD02065 | DC.. | 2 | | 115-199 | | | | | | |
| 0010 | 22 | GA | 4-3 | 22-12-11 | D00211B | K06 | | | D41325J | 14 | | | ALL | | | | | | |
| 0011 | 22 | GA | 3-3 | 34-33-11 | D00211B | F05 | | | GD02065 | DC.. | 2 | | 001-099 | | | | | | |
| 0011 | 24 | GK | 3-3 | 34-33-11 | D00211B | F05 | | | GD02065 | DC.. | 2 | | 115-199 | | | | | | |
| 0012 | 22 | GA | 3-9 | 22-24-11 | D03312B | A08 | | | D42187J | 5 | | | ALL | | | | | | |
| 0013 | 22 | GA | 3-6 | 27-23-11 | D41630J | 13 | | | D42187J | 41 | | | 115-199 | | | | | | |
| 0014 | 22 | GA | 3-6 | 27-23-11 | D41630J | 14 | | | D42187J | 40 | | | 115-199 | | | | | | |
| 0015 | 22 | GA | 3-6 | 27-23-11 | D41630J | 15 | | | D42187J | 39 | | | 115-199 | | | | | | |
| 0019 | 20 | GA | 2-10 | 21-31-11 | D02340A | | | FK | GD02061 | ST.. | 2 | | ALL | | | | | | |
| 0020 | 22 | GA | 2-10 | 21-31-11 | D02340A | C12 | | | GD02061 | DC.. | 2 | | ALL | | | | | | |
| 0021 | 20 | GA | 3-6 | 21-31-11 | D41924J | 1 | | | TB0183Y | A013 | BJ | | ALL | | | | | | |
| 0022 | 20 | GA | 2-10 | 21-31-11 | D41864J | 9 | | | TB0183Y | A013 | BJ | | ALL | | | | | | |
| 0023 | 24 | GK | 2-7 | 21-31-11 | D02340A | B02 | | | TB0183Y | A012 | BJ | | ALL | | | | | | |
| 0024 | 24 | GK | 2-10 | 21-31-11 | D41864J | 7 | | | TB0183Y | A012 | BJ | | ALL | | | | | | |
| 0025 | 24 | GK | 3-0 | 21-31-11 | D41864J | 8 | | | D02340A | A02 | | | ALL | | | | | | |
| 0026 | 24 | GK | 3-2 | 21-31-11 | D41325J | 36 | | | D02340A | B08 | | | ALL | | | | | | |
| 0027 | 22 | GA | 3-9 | 27-41-11 | D03312B | C08 | | | D42187J | 19 | | | ALL | | | | | | |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 25

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | 286N1282 | | | E5-1 SHELF (continued) | | | | | | | | | | | |
| 0029 | 24 | | GK | | 0-7 | 21-31-11 | D02340A | D10 | | | D02340A | D11 | | | 001-003, 005, 007-008, 115-199 |
| 0029 | 24 | | GK | | 0-7 | 21-31-11 | D02340A | D12 | | | D02340A | D11 | | | 004, 006 |
| 0029 | 24 | | GK | | 2-8 | 21-31-11 | D02340A | D11 | | | TB0183X | B049 | BJ | | 009-099 |
| 0030 | 24 | | GK | | 3-0 | 21-31-11 | D41864J | 6 | | | D02340A | D02 | | | ALL |
| 0031 | 22 | | GA | | 2-7 | 21-31-11 | D02340A | A15 | | | TB0183Y | A013 | BJ | | ALL |
| 0032 | 22 | | GA | | 2-10 | 21-31-11 | D02340A | D15 | | | GD02061 | AC.. | 2 | | ALL |
| 0033 | 24 | | GK | | 2-5 | 21-31-21 | D42187J | 13 | | | TB0183Y | A012 | BJ | | ALL |
| 0035 | 24 | | GK | | 0-7 | 27-58-31 | D03312A | H10 | | | D03312A | H08 | | | 001-099 |
| 0035 | 22 | | GA | | 0-7 | 27-58-31 | D03312A | H10 | | | D03312A | H08 | | | 115-199 |
| 0036 | 24 | | GK | | 0-7 | 27-58-31 | D03312A | A11 | | | D03312A | A08 | | | 001-099 |
| 0036 | 22 | | GA | | 0-7 | 27-58-31 | D03312A | A11 | | | D03312A | A08 | | | 115-199 |
| 0037 | 24 | | GK | | 2-11 | 27-58-31 | D03312A | K15 | | | GD02064 | ST.. | 2 | | 001-099 |
| 0037 | 22 | | GA | | 2-11 | 27-58-31 | D03312A | K15 | | | GD02064 | ST.. | 2 | | 115-199 |
| 0040 | 24 | | GK | | 2-10 | 27-58-31 | D03312A | C09 | | | D41377J | 5 | | | ALL |
| 0042 | 24 | | GK | | 3-11 | 27-58-31 | D41652J | 3 | | | D03312B | D11 | | | ALL |
| 0044 | 24 | | GK | | 3-9 | 27-58-31 | D03312B | E11 | | | D41325J | 30 | | | ALL |
| 0045 | 22 | | GA | | 3-6 | 24-22-22 | D01850A | A01 | | | D41377J | 48 | | | 001-099 |
| 0046 | 22 | | GA | | 3-4 | 24-21-41 | D01850B | A15 | | | D42118J | 1 | | | 001-099 |
| 0047 | 22 | | GA | | 3-4 | 24-21-41 | D01850B | B15 | | | D42118J | 2 | | | 001-099 |
| 0048 | 22 | | GA | | 3-4 | 24-21-41 | D01850B | C15 | | | D42118J | 3 | | | 001-099 |
| 0049 | 22 | | GA | | 3-9 | 33-31-31 | D42118J | 15 | | | D42120J | 11 | | | 001-099 |
| 0050 | 24 | | GK | | 4-1 | 24-28-21 | D01850A | B02 | | | TB0183Y | A002 | BJ | | 001-099 |
| 0051 | 24 | | GK | | 4-1 | 24-28-21 | D01850A | A10 | | | TB0183Y | A002 | BJ | | 001-099 |
| 0052 | 24 | | GK | | 2-7 | 24-28-21 | TB0183Y | A002 | BJ | | D41459J | 25 | | | 001-099 |
| 0053 | 24 | | GK | | 3-6 | 24-41-11 | D01850A | D07 | | | D42118J | 14 | | | 001-099 |
| 0061 | 22 | | GA | | 3-9 | 22-12-11 | D03312B | E13 | | | D41325J | 4 | | | ALL |
| 0062 | 22 | | GA | | 3-9 | 22-12-11 | D03312B | F13 | | | D41325J | 46 | | | ALL |
| 0063 | 24 | | GK | | 2-7 | 24-28-21 | D41459J | 8 | | | TB0183Y | A001 | BJ | | ALL |
| 0064 | 24 | | GK | | 3-0 | 24-28-21 | D02108A | B02 | | | TB0183Y | A001 | BJ | | ALL |
| 0065 | 24 | | GK | | 3-0 | 24-28-21 | D02108A | A10 | | | TB0183Y | A001 | BJ | | ALL |
| 0077 | 22 | | GA | | 2-9 | 24-21-11 | D41742J | 8 | | | D02108B | A15 | | | ALL |
| 0078 | 22 | | GA | | 2-9 | 24-21-11 | D41742J | 6 | | | D02108B | B15 | | | ALL |
| 0079 | 22 | | GA | | 2-9 | 24-21-11 | D41742J | 10 | | | D02108B | C15 | | | ALL |
| 0083 | 22 | | GA | | 2-11 | 24-22-12 | D41864J | 1 | | | D02108A | D08 | | | ALL |
| 0084 | 22 | | GA | | 2-11 | 24-22-12 | D41742J | 2 | | | D02108A | A06 | | | ALL |
| 0085 | 22 | | GA | | 2-11 | 24-22-12 | D41742J | 23 | | | D02108A | C08 | | | ALL |
| 0086 | 22 | | GA | | 2-11 | 24-22-12 | D41742J | 24 | | | D02108A | A08 | | | ALL |
| 0087 | 22 | | GA | | 2-11 | 24-22-12 | D41742J | 25 | | | D02108A | C07 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 26

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | | 286N1282 | | | | E5-1 SHELF (continued) | | | | | | | | | |
| 0088 | 22 | GA | | | 2-11 | 24-22-12 | D41742J | | 4 | | D02108A | D15 | | | ALL |
| 0089 | 22 | GA | | | 2-11 | 24-22-12 | D41742J | | 21 | | D02108A | D05 | | | ALL |
| 0090 | 22 | GA | | | 2-11 | 24-22-11 | D41742J | | 1 | | D02108A | C15 | | | ALL |
| 0091 | 22 | GA | | | 2-11 | 24-22-11 | D41742J | | 9 | | D02108A | D06 | | | ALL |
| 0092 | 24 | GK | | | 2-7 | 24-11-11 | D41894J | | 2 | | TB0183Y | C011 | BJ | | ALL |
| 0093 | 22 | GA | | | 2-11 | 24-22-11 | D41742J | | 31 | | D02108A | C01 | | | ALL |
| 0094 | 22 | GA | | | 2-11 | 24-22-11 | D41742J | | 32 | | D02108A | B01 | | | ALL |
| 0095 | 22 | GA | | | 2-11 | 24-22-11 | D41742J | | 22 | | D02108A | C05 | | | ALL |
| 0096 | 22 | GA | | | 2-11 | 24-22-11 | GD02062 | DC.. | 2 | | D02108A | A07 | | | ALL |
| 0097 | 22 | GA | | | 2-11 | 24-22-11 | GD02062 | DC.. | 2 | | D02108A | A11 | | | ALL |
| 0098 | 22 | GA | | | 2-11 | 24-22-11 | D41864J | | 10 | | D02108A | B05 | | | ALL |
| 0099 | 22 | GA | | | 2-9 | 24-22-11 | TB0183Y | C019 | BJ | | D02108B | D02 | | | ALL |
| 0100 | 22 | GA | | | 2-11 | 24-22-11 | D41864J | | 18 | | D02108A | C02 | | | ALL |
| 0101 | 22 | GA | | | 2-11 | 24-22-11 | D41864J | | 21 | | D02108A | A05 | | | 001-003, 115-199 |
| 0102 | 22 | GA | | | 2-11 | 24-22-11 | D41864J | | 20 | | D02108A | D04 | | | 001-003, 115-199 |
| 0103 | 22 | GA | | | 3-0 | 24-22-22 | D41377J | | 10 | | D02108A | A01 | | | ALL |
| 0113 | 24 | GK | | | 3-9 | 31-51-41 | D03312B | E08 | | | D41325J | 5 | | | ALL |
| 0114 | 24 | GK | | | 3-9 | 31-51-42 | D03312B | G08 | | | D41325J | 9 | | | ALL |
| 0116 | 24 | GK | | | 2-4 | 27-32-21 | D41864J | | 5 | | D41377J | 7 | | | ALL |
| 0117 | 24 | GK | | | 2-10 | 27-32-21 | D03312A | F09 | | | D41377J | 1 | | | ALL |
| 0118 | 24 | GK | | | 3-2 | 31-31-31 | D41459J | | 1 | | D03312B | J10 | | | ALL |
| 0119 | 24 | GK | | | 3-2 | 31-31-61 | D41459J | | 2 | | D03312B | B10 | | | 001-099 |
| 0119 | 24 | GK | | | 3-2 | 31-31-31 | D41459J | | 2 | | D03312B | B10 | | | 115-199 |
| 0120 | 24 | GK | | | 3-2 | 31-31-61 | D41459J | | 3 | | D03312B | C11 | | | 001-099 |
| 0120 | 24 | GK | | | 3-2 | 31-31-31 | D41459J | | 3 | | D03312B | C11 | | | 115-199 |
| 0121 | 24 | GK | | | 3-2 | 31-31-61 | D41459J | | 4 | | D03312B | F10 | | | 001-099 |
| 0121 | 24 | GK | | | 3-2 | 31-31-31 | D41459J | | 4 | | D03312B | F10 | | | 115-199 |
| 0124 | 22 | GA | | | 2-9 | 24-11-11 | D41894J | | 5 | | D02108B | A03 | | | ALL |
| 0125 | 22 | GA | | | 2-10 | 24-11-11 | GD02062 | DC.. | 2 | | D02108B | D15 | | | ALL |
| 0126 | 22 | GA | | | 2-10 | 24-11-11 | GD02062 | ST.. | 2 | | D02108B | A08 | | | ALL |
| 0127 | 20 | GA | | | 2-11 | 24-11-11 | D41864J | | 38 | | TB0183Y | A011 | BJ | | ALL |
| 0128 | 22 | GA | | | 3-0 | 24-11-11 | D02108A | D02 | | | TB0183Y | A011 | BJ | | ALL |
| 0129 | 22 | GA | | | 2-11 | 24-11-11 | D02108A | C04 | | | D41864J | 23 | | | ALL |
| 0130 | 24 | GK | | | 3-0 | 24-11-11 | D02108A | A02 | | | TB0183Y | C011 | BJ | | ALL |
| 0131 | 24 | GK | | | 2-11 | 24-11-11 | D41864J | | 27 | | D02108A | D10 | | | ALL |
| 0132 | 24 | GK | | | 2-11 | 24-11-11 | D41864J | | 26 | | TB0183Y | C011 | BJ | | ALL |
| 0133 | 24 | GK | | | 2-9 | 24-11-11 | D41864J | | 28 | | D02108B | D08 | | | ALL |
| 0134 | 24 | GK | | | 3-9 | 31-51-42 | D41325J | | 10 | | D03312B | B08 | | | ALL |
| 0135 | 24 | GK | | | 2-10 | 24-11-11 | D02108A | C06 | | | D41898J | 27 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 27

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | 286N1282 | | | | E5-1 SHELF (continued) | | | | | | | | | | | |
| 0136 | 24 | | GK | | 2-11 | 24-11-11 | | D41864J | 25 | | | TB0183Y | C011 | BJ | | ALL |
| 0137 | 20 | | GA | | 2-7 | 24-11-11 | | TB0183Y | A011 | BJ | | D41898J | 8 | | | ALL |
| 0139 | 24 | | GK | | 3-0 | 24-11-11 | | D41864J | 29 | | | D02108A | D13 | | | ALL |
| 0153 | 22 | | GA | | 3-2 | 34-46-12 | | D03312B | H08 | | | D41459J | 13 | | | ALL |
| 0154 | 20 | | GA | | 2-5 | 34-33-11 | | D41325J | | | AA | GD02060 | ST.. | 2 | | ALL |
| 0162 | 12 | | GA | | 2-1 | 27-51-41 | | D03312C | 8 | | | GD03033 | DC.. | E | | ALL |
| 0163 | 24 | | GK | | 4-0 | 27-51-41 | | D03312A | H03 | | | D41882J | 9 | | | ALL |
| 0168 | 24 | | GK | | 2-7 | 27-51-41 | | D41696J | 4 | | | D42069J | 1 | | | ALL |
| 0169 | 24 | | GK | | 2-4 | 27-51-41 | | D41325J | 24 | | | TB0183Y | C007 | BJ | | ALL |
| 0170 | 24 | | GK | | 2-4 | 27-51-41 | | D41325J | 25 | | | TB0183Y | A008 | BJ | | ALL |
| 0171 | 24 | | GK | | 2-4 | 27-51-41 | | D41325J | 26 | | | TB0183Y | C008 | BJ | | ALL |
| 0172 | 22 | | GA | | 3-3 | 27-51-21 | | D03312B | E06 | | | TB0183Y | A020 | BJ | | ALL |
| 0175 | 22 | | GA | | 3-5 | 27-51-21 | | TB0183Y | C003 | BJ | | D03312A | A09 | | | 001-099 |
| 0175 | 22 | | GA | | 2-10 | 27-51-21 | | D41377J | 18 | | | D03312A | A09 | | | 115-199 |
| 0176 | 22 | | GA | | 3-5 | 27-51-21 | | TB0183Y | C002 | BJ | | D03312A | B09 | | | 001-099 |
| 0176 | 22 | | GA | | 2-10 | 27-51-21 | | D41377J | 17 | | | D03312A | B09 | | | 115-199 |
| 0177 | 24 | | GK | | 3-11 | 27-51-31 | | D41652J | 17 | | | D03312B | B05 | | | ALL |
| 0178 | 22 | | GA | | 3-11 | 27-51-31 | | D41652J | 18 | | | D03312B | A05 | | | ALL |
| 0180 | 24 | | GK | | 4-0 | 27-51-31 | | D40029J | 4 | | | D03312A | E09 | | | ALL |
| 0181 | 24 | | GK | | 4-0 | 27-51-41 | | D41882J | 6 | | | D03312A | D03 | | | ALL |
| 0182 | 24 | | GK | | 4-0 | 27-51-41 | | D41882J | 8 | | | D03312A | F03 | | | ALL |
| 0183 | 22 | | GA | | 2-11 | 27-51-41 | | GD02064 | AC.. | 2 | | D03312A | D04 | | | ALL |
| 0184 | 22 | | GA | | 2-11 | 27-51-41 | | GD02064 | AC.. | 2 | | D03312A | F04 | | | ALL |
| 0186 | 24 | | GK | | 3-6 | 27-51-41 | | D42069J | 2 | | | TB0183Y | C007 | BJ | | ALL |
| 0187 | 24 | | GK | | 2-5 | 27-51-41 | | D41652J | 20 | | | TB0183Y | A008 | BJ | | ALL |
| 0188 | 24 | | GK | | 2-5 | 27-51-41 | | D41652J | 21 | | | TB0183Y | C008 | BJ | | ALL |
| 0189 | 24 | | GK | | 2-6 | 27-51-41 | | D41652J | 22 | | | TB0183Y | A009 | BJ | | ALL |
| 0190 | 24 | | GK | | 2-6 | 27-51-41 | | D41652J | 23 | | | TB0183Y | C009 | BJ | | ALL |
| 0203 | 24 | | GK | | 2-6 | 27-58-11 | | TB0183Y | C010 | BJ | | D41652J | 24 | | | ALL |
| 0204 | 24 | | GK | | 3-4 | 27-58-11 | | TB0183Y | C010 | BJ | | D03312B | H05 | | | ALL |
| 0205 | 24 | | GK | | 2-4 | 27-58-11 | | TB0183Y | C010 | BJ | | D41325J | 29 | | | ALL |
| 0206 | 22 | | GA | | 3-11 | 27-51-51 | | D41652J | 29 | | | D03312B | F05 | | | ALL |
| 0207 | 22 | | GA | | 3-6 | 27-23-21 | | D42187J | 6 | | | D41630J | 8 | | | ALL |
| 0208 | 22 | | GA | | 3-6 | 27-23-21 | | D42187J | 7 | | | D41630J | 9 | | | ALL |
| 0209 | 22 | | GA | | 3-6 | 27-23-21 | | D42187J | 8 | | | D41630J | 10 | | | ALL |
| 0210 | 22 | | GA | | 3-6 | 27-23-21 | | D42187J | 9 | | | D41630J | 11 | | | ALL |
| 0211 | 22 | | GA | | 2-10 | 24-22-11 | | D02108B | A07 | | | GD02062 | DC.. | 2 | | ALL |
| 0221 | 24 | | GK | | 2-10 | 27-81-21 | | D41377J | 6 | | | D03312A | H09 | | | ALL |
| 0226 | 22 | | GA | | 2-11 | 27-81-21 | | D41696J | 1 | | | D03312B | D05 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 28

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | 286N1282 | | | E5-1 SHELF (continued) | | | | | | | | | | | |
| 0227 | 22 | | GA | | 2-11 | 27-81-21 | D41696J | 2 | | | D03312B | E05 | | | ALL |
| 0228 | 24 | | GK | | 2-4 | 27-51-41 | D41325J | 27 | | | TB0183Y | A009 | BJ | | ALL |
| 0229 | 24 | | GK | | 2-4 | 27-51-41 | D41325J | 28 | | | TB0183Y | C009 | BJ | | ALL |
| 0236 | 22 | | GA | | 2-10 | 27-51-51 | D03312A | D09 | | | D41377J | 9 | | | ALL |
| 0240 | 24 | | GK | | 2-8 | 21-31-11 | TB0183X | C049 | BJ | | D02340A | D12 | | | 009-099 |
| 0244 | 22 | | GA | | 3-11 | 27-51-51 | D41652J | 25 | | | D03312B | C05 | | | ALL |
| 0248 | 24 | | GK | | 2-10 | 24-27-11 | D02108A | D07 | | | D41459J | 5 | | | ALL |
| 0249 | 24 | | GK | | 2-10 | 24-27-11 | D41742J | 19 | | | D41459J | 6 | | | ALL |
| 0250 | 24 | | GK | | 2-10 | 24-27-11 | D41742J | 20 | | | D41459J | 7 | | | ALL |
| 0251 | 24 | | GK | | 3-3 | 27-51-41 | D03312B | A06 | | | TB0183Y | C008 | BJ | | ALL |
| 0252 | 24 | | GK | | 3-3 | 27-51-41 | D03312B | B06 | | | TB0183Y | A008 | BJ | | ALL |
| 0253 | 24 | | GK | | 3-4 | 27-51-41 | D03312B | J05 | | | TB0183Y | C009 | BJ | | ALL |
| 0254 | 24 | | GK | | 3-4 | 27-51-41 | D03312B | K05 | | | TB0183Y | A009 | BJ | | ALL |
| 0255 | 24 | | GK | | 2-11 | 27-51-41 | D03312B | D06 | | | D41696J | 5 | | | ALL |
| 0256 | 24 | | GK | | 3-3 | 27-51-41 | D03312B | C06 | | | TB0183Y | C007 | BJ | | ALL |
| 0257 | 22 | | GA | | 3-6 | 24-22-41 | D01850B | A03 | | | D41920J | 1 | | | 001-099 |
| 0258 | 22 | | GA | | 3-6 | 24-22-41 | D01850B | D02 | | | D42368J | 1 | | | 001-099 |
| 0259 | 24 | | GK | | 3-7 | 24-22-41 | D01850A | B05 | | | D42368J | 2 | | | 001-099 |
| 0260 | 24 | | GK | | 3-7 | 24-22-41 | D01850A | A05 | | | D42368J | 3 | | | 001-003 |
| 0261 | 24 | | GK | | 3-7 | 24-22-41 | D01850A | D04 | | | D42368J | 4 | | | 001-003 |
| 0262 | 24 | | GK | | 2-7 | 24-22-41 | D42368J | 5 | | | D42118J | 9 | | | 001-099 |
| 0263 | 22 | | GA | | 2-11 | 24-22-41 | D01850A | A06 | | | D41912J | 1 | | | 001-099 |
| 0264 | 24 | | GK | | 3-7 | 24-22-41 | D01850A | C02 | | | D42368J | 6 | | | 001-099 |
| 0265 | 22 | | GA | | 3-6 | 24-22-41 | D01850A | C05 | | | D42118J | 8 | | | 001-099 |
| 0266 | 22 | | GA | | 3-6 | 24-22-41 | D01850A | B01 | | | D42118J | 5 | | | 001-099 |
| 0267 | 22 | | GA | | 3-6 | 24-22-41 | D01850A | C01 | | | D42118J | 6 | | | 001-099 |
| 0268 | 24 | | GK | | 3-6 | 24-22-41 | D01850A | D06 | | | D42118J | 7 | | | 001-099 |
| 0269 | 22 | | GA | | 3-6 | 24-22-41 | D01850A | C15 | | | D42118J | 4 | | | 001-099 |
| 0270 | 22 | | GA | | 4-2 | 24-22-41 | D01850A | A11 | | | GD02060 | DC.. | 2 | | 001-099 |
| 0271 | 22 | | GA | | 4-0 | 24-22-41 | D01850B | A08 | | | GD02060 | ST.. | 2 | | 001-099 |
| 0272 | 22 | | GA | | 4-0 | 24-22-41 | D01850B | D15 | | | GD02060 | DC.. | 2 | | 001-099 |
| 0276 | 22 | | GA | | 2-11 | 24-22-11 | D02108A | A03 | | | TB0183Y | C019 | BJ | | ALL |
| 0278 | 24 | | GK | | 0-7 | 21-31-11 | TB0183X | B049 | BJ | | TB0183X | A049 | BJ | | 009-099 |
| 0279 | 22 | | GA | | 2-10 | 24-22-11 | D41864J | 11 | | | TB0183Y | C019 | BJ | | ALL |
| 0280 | 24 | | GK | | 3-9 | 31-51-41 | D03312B | G10 | | | D41325J | 6 | | | ALL |
| 0283 | 24 | | GK | | 2-8 | 21-31-11 | D02340A | D10 | | | TB0183X | A049 | BJ | | 009-099 |
| 0288 | 20 | | GA | | 2-11 | 21-31-21 | D41864J | 12 | | | D41696J | 7 | | | ALL |
| 0289 | 24 | | GK | | 2-11 | 21-31-21 | D41864J | 19 | | | D41696J | 8 | | | ALL |
| 0290 | 24 | | GK | | 2-11 | 21-31-21 | D41864J | 22 | | | D41696J | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 29

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1282 | 286N1282 | | | | E5-1 SHELF (continued) | | | | | | | | | | | | |
| 0291 | 22 | | GA | | 3-0 | 27-81-31 | D41630J | | 7 | | | TB0183Y | A019 | BJ | | ALL | |
| 0292 | 22 | | GA | | 3-0 | 27-81-31 | D41377J | | 28 | | | TB0183Y | A019 | BJ | | ALL | |
| 0293 | 22 | | GA | | 3-4 | 27-81-31 | D03312A | | G09 | | | TB0183Y | A019 | BJ | | ALL | |
| 0294 | 22 | | GA | | 2-7 | 74-31-11 | D41459J | | 12 | | | TB0183Y | C001 | BJ | | 001-099 | |
| 0294 | 22 | | GA | | 3-9 | 74-31-11 | D42187J | | 18 | | | D03312B | C10 | | | 115-199 | |
| 0295 | 22 | | GA | | 2-8 | 21-31-11 | D02340A | | B12 | | | GD02065 | ST.. | 2 | | ALL | |
| 0297 | 24 | | GK | | 1-9 | 27-51-31 | D41652J | | 30 | | | D40029J | 1 | | | 001-099 | |
| 0297 | 22 | | GA | | 1-9 | 27-51-31 | D41652J | | 30 | | | D40029J | 1 | | | 115-199 | |
| 0298 | 22 | | GA | | 1-9 | 27-51-31 | D41652J | | 31 | | | D40029J | 2 | | | ALL | |
| 0299 | 24 | | GK | | 3-8 | 27-51-31 | D41377J | | 16 | | | D40029J | 3 | | | 001-099 | |
| 0299 | 22 | | GA | | 3-8 | 27-51-31 | D41377J | | 16 | | | D40029J | 3 | | | 115-199 | |
| 0320 | 24 | | GK | | 2-7 | 31-31-63 | D41459J | | 26 | | | TB0183Y | C003 | BJ | | 001-099 | |
| 0350 | 22 | | GA | | 2-7 | 74-31-11 | D41459J | | 35 | | | TB0183Y | C001 | BJ | | 001-099 | |
| 0351 | 22 | | GA | | 3-4 | 74-31-11 | TB0183Y | | C001 | BJ | | D03312B | C10 | | | 001-099 | |
| 0362 | 24 | | GK | | 2-9 | 27-32-21 | D03312B | | A10 | | | D41377J | 42 | | | ALL | |
| 0365 | 24 | | GK | | 2-9 | 27-32-21 | D41377J | | 45 | | | D03312B | H10 | | | 001-099 | |
| 0368 | 24 | | GK | | 2-9 | 27-32-21 | D41377J | | 41 | | | D03312B | E10 | | | 001-099 | |
| 0380 | 24 | | GK | | 2-7 | 31-31-63 | D41459J | | 27 | | | TB0183Y | C002 | BJ | | 001-099 | |
| 0386 | 22 | | GA | | 3-0 | 27-81-31 | TB0183Y | | A019 | BJ | | D41377J | 46 | | | ALL | |
| 0387 | 22 | | GA | | 3-0 | 27-51-21 | TB0183Y | | A020 | BJ | | D41377J | 47 | | | ALL | |
| 0388 | 22 | | GA | | 3-7 | 27-51-21 | TB0183Y | | A020 | BJ | | D41696J | 6 | | | ALL | |
| 0389 | 22 | | GA | | 3-9 | 34-45-01 | D41325J | | 7 | | | D03312B | CAP | Y | | 001-002, 115-199 | |
| 0398 | 22 | | GA | | 3-1 | 27-51-21 | D41377J | | 18 | | | TB0183Y | C003 | BJ | | 001-099 | |
| 0399 | 22 | | GA | | 3-1 | 27-51-21 | D41377J | | 17 | | | TB0183Y | C002 | BJ | | 001-099 | |
| 2001B | 24 | | GL | CA | 3-2 | 31-31-51 | D41459J | | 24 | | | D03312B | B13 | | | 001-099 | |
| 2001B | 24 | | GL | AQ | 3-2 | 31-31-31 | D41459J | | 24 | | | D03312B | B13 | | | 115-199 | |
| 2001R | 24 | | GL | CA | 0-0 | 31-31-51 | D41459J | | 23 | | | D03312B | A13 | | | 001-099 | |
| 2001R | 24 | | GL | AQ | 0-0 | 31-31-31 | D41459J | | 23 | | | D03312B | A13 | | | 115-199 | |
| 2002B | 22 | | GB | AB | 3-9 | 21-31-11 | D41924J | | 6 | | | D02340A | C13 | | | ALL | |
| 2002R | 22 | | GB | AB | 0-0 | 21-31-11 | D41924J | | 5 | | | D02340A | B13 | | | ALL | |
| 2003B | 24 | | GL | AR | 3-9 | 21-31-11 | D02340A | | A10 | | | D41924J | 9 | | | ALL | |
| 2003R | 24 | | GL | AR | 0-0 | 21-31-11 | D02340A | | A11 | | | D41924J | 8 | | | ALL | |
| 2004B | 24 | | GL | AU | 3-2 | 21-31-21 | D42187J | | 15 | | | D02340A | D04 | | | ALL | |
| 2004R | 24 | | GL | AU | 0-0 | 21-31-21 | D42187J | | 14 | | | D02340A | D03 | | | ALL | |
| 2005B | 24 | | GL | AV | 3-2 | 21-31-21 | D42187J | | 17 | | | D02340A | C03 | | | ALL | |
| 2005R | 24 | | GL | AV | 0-0 | 21-31-21 | D42187J | | 16 | | | D02340A | C04 | | | ALL | |
| 2009B | 24 | | GL | BJ | 2-10 | 24-11-11 | D02108A | | B09 | | | D41898J | 19 | | | ALL | |
| 2009R | 24 | | GL | BJ | 0-0 | 24-11-11 | D02108A | | A09 | | | D41898J | 18 | | | ALL | |
| 2010B | 24 | | GL | BK | 2-10 | 24-11-11 | D02108A | | D01 | | | D41898J | 7 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 30

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | 286N1282 | | | E5-1 SHELF (continued) | | | | | | | | | | | |
| 2010R | 24 | GL | BK | | 0-0 | 24-11-11 | D02108A | D03 | | | D41898J | 15 | | | ALL |
| 2012B | 24 | GL | AI | | 3-9 | 22-32-13 | D03312B | D13 | | | D42187J | 21 | | | ALL |
| 2012R | 24 | GL | AI | | 0-0 | 22-32-13 | D03312B | C13 | | | D42187J | 20 | | | ALL |
| 2017B | 24 | GL | BX | | 2-7 | 27-51-41 | D41654J | 2 | | | D03312B | D03 | | | ALL |
| 2017R | 24 | GL | BX | | 0-0 | 27-51-41 | D41654J | 1 | | | D03312B | C03 | | | ALL |
| 2018B | 24 | GL | BZ | | 2-7 | 27-51-41 | D41654J | 8 | | | D03312B | H03 | | | ALL |
| 2018R | 24 | GL | BZ | | 0-0 | 27-51-41 | D41654J | 7 | | | D03312B | G03 | | | ALL |
| 2019B | 24 | GL | CB | | 2-9 | 27-51-41 | D41630J | 5 | | | D03312B | F03 | | | ALL |
| 2019R | 24 | GL | CB | | 0-0 | 27-51-41 | D41630J | 6 | | | D03312B | E03 | | | ALL |
| 2020B | 24 | GL | CD | | 2-9 | 27-51-41 | D42228J | 2 | | | D03312B | K03 | | | ALL |
| 2020R | 24 | GL | CD | | 0-0 | 27-51-41 | D42228J | 1 | | | D03312B | J03 | | | ALL |
| 2021B | 24 | GL | CF | | 3-11 | 27-51-41 | D41652J | 27 | | | D03312B | B03 | | | ALL |
| 2021R | 24 | GL | CF | | 0-0 | 27-51-41 | D41652J | 28 | | | D03312B | A03 | | | ALL |
| 2039B | 24 | GL | AC | | 3-2 | 21-31-11 | D41325J | 38 | | | D02340A | A07 | | | ALL |
| 2039R | 24 | GL | AC | | 0-0 | 21-31-11 | D41325J | 37 | | | D02340A | A08 | | | ALL |
| 2040B | 24 | GL | BQ | | 2-9 | 27-32-21 | D41377J | 40 | | | D03312B | H13 | | | 001-099 |
| 2040R | 24 | GL | BQ | | 0-0 | 27-32-21 | D41377J | 39 | | | D03312B | G13 | | | 001-099 |
| 2504B | 24 | G2 | AN | | 3-9 | 21-31-11 | D02340A | C11 | | | D41924J | 3 | | | ALL |
| 2504R | 24 | G2 | AN | | 0-0 | 21-31-11 | D02340A | B11 | | | D41924J | 2 | | | ALL |
| 2504Z | | | AN | | 0-0 | 21-31-11 | GD02064 | ST.. | 2 | | D41924J | 4 | | | ALL |
| 2505B | 22 | GU | AZ | | 2-9 | 24-21-11 | D41898J | 10 | | | D02108B | B01 | | | ALL |
| 2505R | 22 | GU | AZ | | 0-0 | 24-21-11 | D41898J | 9 | | | D02108B | A01 | | | ALL |
| 2505Z | | | AZ | | 0-0 | 24-21-11 | D41898J | 11 | | | D02108B | C01 | | | ALL |
| 2506B | 22 | GU | BI | | 4-8 | 24-21-41 | D01850B | B01 | | | D42120J | 9 | | | 001-099 |
| 2506R | 22 | GU | BI | | 0-0 | 24-21-41 | D01850B | A01 | | | D42120J | 8 | | | 001-099 |
| 2506Z | | | BI | | 0-0 | 24-21-41 | D01850B | C01 | | | D42120J | 10 | | | 001-099 |
| 2508B | 24 | G2 | BL | | 2-10 | 24-11-11 | D02108A | B04 | | | D41898J | 22 | | | ALL |
| 2508R | 24 | G2 | BL | | 0-0 | 24-11-11 | D02108A | A04 | | | D41898J | 20 | | | ALL |
| 2508Z | | | BL | | 0-0 | 24-11-11 | D02108A | C11 | | | D41898J | 5 | | | ALL |
| 3002B | 18 | GC | AY | | 2-7 | 24-21-11 | D41898J | 1 | | | D02108C | 3 | | | ALL |
| 3002R | 18 | GC | AY | | 0-0 | 24-21-11 | D41898J | 4 | | | D02108C | 2 | | | ALL |
| 3002Y | 18 | GC | AY | | 0-0 | 24-21-11 | D41898J | 2 | | | D02108C | 4 | | | ALL |
| 3003B | 20 | GC | BU | | 4-6 | 24-21-41 | D01850C | 3 | | | D42120J | 2 | | | 001-099 |
| 3003R | 20 | GC | BU | | 0-0 | 24-21-41 | D01850C | 2 | | | D42120J | 1 | | | 001-099 |
| 3003Y | 20 | GC | BU | | 0-0 | 24-21-41 | D01850C | 4 | | | D42120J | 3 | | | 001-099 |
| 4001B | 24 | GN | BA | | 2-9 | 24-21-11 | D41898J | 13 | | | D02108B | B13 | | | ALL |
| 4001G | 24 | GN | BA | | 0-0 | 24-21-11 | D41898J | 3 | | | D02108B | D13 | | | ALL |
| 4001R | 24 | GN | BA | | 0-0 | 24-21-11 | D41898J | 12 | | | D02108B | A13 | | | ALL |
| 4001Y | 24 | GN | BA | | 0-0 | 24-21-11 | D41898J | 14 | | | D02108B | C13 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 31

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | 286N1282 | | | E5-1 SHELF (continued) | | | | | | | | | | | |
| 4002B | 24 | GN | BV | | 4-8 | 24-21-41 | D01850B | B13 | | | D42120J | 5 | | | 001-099 |
| 4002G | 24 | GN | BV | | 0-0 | 24-21-41 | D01850B | D13 | | | D42120J | 7 | | | 001-099 |
| 4002R | 24 | GN | BV | | 0-0 | 24-21-41 | D01850B | A13 | | | D42120J | 4 | | | 001-099 |
| 4002Y | 24 | GN | BV | | 0-0 | 24-21-41 | D01850B | C13 | | | D42120J | 6 | | | 001-099 |
| 4003B | 24 | GN | CU | | 2-9 | 24-23-11 | D41752J | 3 | | | D02108B | C11 | | | ALL |
| 4003G | 24 | GN | CU | | 0-0 | 24-23-11 | D41752J | 4 | | | D02108B | D11 | | | ALL |
| 4003R | 24 | GN | CU | | 0-0 | 24-23-11 | D41752J | 1 | | | D02108B | A11 | | | ALL |
| 4003Y | 24 | GN | CU | | 0-0 | 24-23-11 | D41752J | 2 | | | D02108B | B11 | | | ALL |
| 4004B | 24 | GN | CV | | 3-4 | 24-23-11 | D01850B | C12 | | | D42118J | 11 | | | 001-099 |
| 4004G | 24 | GN | CV | | 0-0 | 24-23-11 | D01850B | D12 | | | D42118J | 10 | | | 001-099 |
| 4004R | 24 | GN | CV | | 0-0 | 24-23-11 | D01850B | A12 | | | D42118J | 13 | | | 001-099 |
| 4004Y | 24 | GN | CV | | 0-0 | 24-23-11 | D01850B | B12 | | | D42118J | 12 | | | 001-099 |
| 4005B | 24 | GN | CW | | 2-9 | 24-23-11 | D41742J | 12 | | | D02108B | C12 | | | ALL |
| 4005G | 24 | GN | CW | | 0-0 | 24-23-11 | D41742J | 11 | | | D02108B | D12 | | | ALL |
| 4005R | 24 | GN | CW | | 0-0 | 24-23-11 | D41742J | 14 | | | D02108B | A12 | | | ALL |
| 4005Y | 24 | GN | CW | | 0-0 | 24-23-11 | D41742J | 13 | | | D02108B | B12 | | | ALL |
| 4006B | 24 | GN | CX | | 2-9 | 24-23-11 | D41742J | 16 | | | D02108B | C10 | | | ALL |
| 4006G | 24 | GN | CX | | 0-0 | 24-23-11 | D41742J | 15 | | | D02108B | D10 | | | ALL |
| 4006R | 24 | GN | CX | | 0-0 | 24-23-11 | D41742J | 18 | | | D02108B | A10 | | | ALL |
| 4006Y | 24 | GN | CX | | 0-0 | 24-23-11 | D41742J | 17 | | | D02108B | B10 | | | ALL |
| 4007B | 24 | GN | DP | | 2-10 | 27-51-41 | D03312A | J06 | | | D42228J | 4 | | | ALL |
| 4007G | 24 | GN | DP | | 0-0 | 27-51-41 | D03312A | K07 | | | D42228J | 6 | | | ALL |
| 4007R | 24 | GN | DP | | 0-0 | 27-51-41 | D03312A | J07 | | | D42228J | 3 | | | ALL |
| 4007Y | 24 | GN | DP | | 0-0 | 27-51-41 | D03312A | K06 | | | D42228J | 5 | | | ALL |
| 4008B | 24 | GN | DQ | | 2-8 | 27-51-41 | D03312A | C07 | | | D41654J | 4 | | | ALL |
| 4008G | 24 | GN | DQ | | 0-0 | 27-51-41 | D03312A | D07 | | | D41654J | 6 | | | ALL |
| 4008R | 24 | GN | DQ | | 0-0 | 27-51-41 | D03312A | C06 | | | D41654J | 3 | | | ALL |
| 4008Y | 24 | GN | DQ | | 0-0 | 27-51-41 | D03312A | D06 | | | D41654J | 5 | | | ALL |
| 4009B | 24 | GN | DR | | 2-8 | 27-51-41 | D03312A | G07 | | | D41654J | 10 | | | ALL |
| 4009G | 24 | GN | DR | | 0-0 | 27-51-41 | D03312A | H07 | | | D41654J | 12 | | | ALL |
| 4009R | 24 | GN | DR | | 0-0 | 27-51-41 | D03312A | G06 | | | D41654J | 9 | | | ALL |
| 4009Y | 24 | GN | DR | | 0-0 | 27-51-41 | D03312A | H06 | | | D41654J | 11 | | | ALL |
| 4010B | 24 | GN | DS | | 2-10 | 27-51-41 | D03312A | E07 | | | D41630J | 1 | | | ALL |
| 4010G | 24 | GN | DS | | 0-0 | 27-51-41 | D03312A | F07 | | | D41630J | 2 | | | ALL |
| 4010R | 24 | GN | DS | | 0-0 | 27-51-41 | D03312A | E06 | | | D41630J | 3 | | | ALL |
| 4010Y | 24 | GN | DS | | 0-0 | 27-51-41 | D03312A | F06 | | | D41630J | 4 | | | ALL |
| 4011B | 24 | GN | DT | | 4-0 | 27-51-41 | D03312A | A07 | | | D41652J | 13 | | | ALL |
| 4011G | 24 | GN | DT | | 0-0 | 27-51-41 | D03312A | B07 | | | D41652J | 14 | | | ALL |
| 4011R | 24 | GN | DT | | 0-0 | 27-51-41 | D03312A | A06 | | | D41652J | 15 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 32

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | 286N1282 | | | E5-1 SHELF (continued) | | | | | | | | | | | |
| 4011Y | 24 | GN | DT | | 0-0 | 27-51-41 | D03312A | B06 | | | D41652J | 16 | | | ALL |
| 4251B | 22 | GW | AK | | 3-0 | 21-31-11 | D41864J | 16 | | | D02340A | B01 | | | ALL |
| 4251G | 22 | GW | AK | | 0-0 | 21-31-11 | D41864J | 14 | | | D02340A | D01 | | | ALL |
| 4251R | 22 | GW | AK | | 0-0 | 21-31-11 | D41864J | 17 | | | D02340A | A01 | | | ALL |
| 4251Y | 22 | GW | AK | | 0-0 | 21-31-11 | D41864J | 15 | | | D02340A | C01 | | | ALL |
| 4251Z | | | AK | | 0-0 | 21-31-11 | D41864J | 13 | | | D02340A | | | FK | ALL |
| 4252B | 22 | GW | AH | | 2-11 | 21-31-21 | D41864J | 30 | | | D41696J | 12 | | | ALL |
| 4252G | 22 | GW | AH | | 0-0 | 21-31-21 | D41864J | 31 | | | D41696J | 25 | | | ALL |
| 4252R | 22 | GW | AH | | 0-0 | 21-31-21 | D41864J | 32 | | | D41696J | 13 | | | ALL |
| 4252Y | 22 | GW | AH | | 0-0 | 21-31-21 | D41864J | 33 | | | D41696J | 11 | | | ALL |
| 4252Z | | | AH | | 0-0 | 21-31-21 | D41864J | 34 | | | D41696J | 24 | | | ALL |
| 5001B | 24 | G2 | AF | | 4-3 | 34-33-11 | D00211B | G03 | | | D41325J | 3 | | | ALL |
| 5001R | 24 | G2 | AF | | 0-0 | 34-33-11 | D00211B | G02 | | | D41325J | 2 | | | ALL |
| 5001Z | | | AF | | 0-0 | 34-33-11 | D00211B | DED | | | D41325J | | | AA | ALL |
| 5002B | 24 | G2 | AG | | 4-3 | 22-12-11 | D00211B | B03 | | | D41325J | 12 | | | ALL |
| 5002R | 24 | G2 | AG | | 0-0 | 22-12-11 | D00211B | B02 | | | D41325J | 11 | | | ALL |
| 5002Z | | | AG | | 0-0 | 22-12-11 | GD02068 | ST.. | 2 | | D41325J | 13 | | | ALL |
| 5004B | 24 | G2 | AJ | | 3-4 | 27-51-51 | D03312A | K13 | | | TB0183Z | 17 | BJ | | ALL |
| 5004R | 24 | G2 | AJ | | 0-0 | 27-51-51 | D03312A | J13 | | | TB0183Z | 18 | BJ | | ALL |
| 5004Z | | | AJ | | 0-0 | 27-51-51 | D03312A | DED | | | GD02062 | ST.. | 2 | | ALL |
| 5005B | 24 | G2 | AM | | 2-7 | 21-31-11 | D02340A | A05 | | | TB0183Z | 17 | BJ | | ALL |
| 5005R | 24 | G2 | AM | | 0-0 | 21-31-11 | D02340A | B06 | | | TB0183Z | 18 | BJ | | ALL |
| 5005Z | | | AM | | 0-0 | 21-31-11 | D02340A | | | FK | GD02062 | ST.. | 2 | | ALL |
| 5006B | 24 | G2 | AL | | 2-7 | 21-31-11 | D02340A | C05 | | | TB0183Y | C013 | BJ | | ALL |
| 5006R | 24 | G2 | AL | | 0-0 | 21-31-11 | D02340A | D06 | | | TB0183Y | C012 | BJ | | ALL |
| 5006Z | | | AL | | 0-0 | 21-31-11 | D02340A | | | FK | GD02061 | ST.. | 2 | | ALL |
| 5007B | 24 | G2 | AS | | 2-11 | 21-31-11 | D41377J | 3 | | | TB0183Y | C013 | BJ | | ALL |
| 5007R | 24 | G2 | AS | | 0-0 | 21-31-11 | D41377J | 2 | | | TB0183Y | C012 | BJ | | ALL |
| 5007Z | | | AS | | 0-0 | 21-31-11 | D41377J | 4 | | | GD02061 | ST.. | 2 | | ALL |
| 5008B | 24 | G2 | AT | | 2-6 | 21-31-21 | D42187J | 11 | | | TB0183Z | 17 | BJ | | ALL |
| 5008R | 24 | G2 | AT | | 0-0 | 21-31-21 | D42187J | 10 | | | TB0183Z | 18 | BJ | | ALL |
| 5008Z | | | AT | | 0-0 | 21-31-21 | D42187J | 12 | | | GD02062 | ST.. | 2 | | ALL |
| 5009B | 24 | G2 | BE | | 3-5 | 24-22-12 | D42187J | 23 | | | D02108A | B12 | | | ALL |
| 5009R | 24 | G2 | BE | | 0-0 | 24-22-12 | D42187J | 24 | | | D02108A | A12 | | | ALL |
| 5009Z | | | BE | | 0-0 | 24-22-12 | D42187J | 25 | | | D02108A | B11 | | | ALL |
| 5010B | 24 | G2 | BG | | 2-6 | 21-31-11 | D41325J | 43 | | | TB0183Z | 17 | BJ | | ALL |
| 5010R | 24 | G2 | BG | | 0-0 | 21-31-11 | D41325J | 42 | | | TB0183Z | 18 | BJ | | ALL |
| 5010Z | | | BG | | 0-0 | 21-31-11 | D41325J | 44 | | | GD02062 | ST.. | 2 | | ALL |
| 5011B | 24 | G2 | BP | | 3-9 | 27-58-31 | D03312B | K13 | | | D41325J | 32 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 33

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1282 | 286N1282 | | | E5-1 SHELF (continued) | | | | | | | | | | | |
| 5011R | 24 | G2 | | BP | 0-0 | 27-58-31 | D03312B | J13 | | | D41325J | 31 | | | ALL |
| 5011Z | | | | BP | 0-0 | 27-58-31 | GD02065 | ST.. | 2 | | D41325J | 33 | | | ALL |
| 5012B | 24 | G2 | | BY | 3-6 | 24-41-11 | D01850A | B12 | | | D41377J | 50 | | | 001-099 |
| 5012R | 24 | G2 | | BY | 0-0 | 24-41-11 | D01850A | A12 | | | D41377J | 49 | | | 001-099 |
| 5012Z | | | | BY | 0-0 | 24-41-11 | D01850A | B11 | | | D41377J | 51 | | | 001-099 |
| 5013B | 24 | G2 | | DU | 2-11 | 21-31-21 | D41377J | 25 | | | TB0183Y | C013 | BJ | | ALL |
| 5013R | 24 | G2 | | DU | 0-0 | 21-31-21 | D41377J | 24 | | | TB0183Y | C012 | BJ | | ALL |
| 5013Z | | | | DU | 0-0 | 21-31-21 | D41377J | 26 | | | GD02061 | ST.. | 2 | | ALL |
| FRAA | | | | | 0-0 | 34-33-11 | D41325J | 1 | | | D41325J | | | AA | ALL |
| W1284 | 286N1284 | | | E5-2 SHELF | | | | | | | | | | | |
| 0001 | 22 | GA | | | 2-11 | 34-33-21 | D00217C | 8 | | | D40710J | 1 | | | 001-099 |
| 0001 | 22 | GA | | | 3-0 | 34-33-21 | D00217C | 8 | | | D40710J | 1 | | | 115-199 |
| 0002 | 20 | GA | | | 3-11 | 34-33-21 | D00217C | 3 | | | GD02076 | AC.. | 2 | | 001-099 |
| 0002 | 20 | GA | | | 4-0 | 34-33-21 | D00217C | 3 | | | GD02076 | AC.. | 2 | | 115-199 |
| 0003 | 20 | GA | | | 3-11 | 34-33-21 | D00217C | 2 | | | GD02076 | DC.. | 2 | | 001-099 |
| 0003 | 20 | GA | | | 4-0 | 34-33-21 | D00217C | 2 | | | GD02076 | DC.. | 2 | | 115-199 |
| 0004 | 24 | GK | | | 0-7 | 34-33-21 | D00217B | J04 | | | D00217B | J06 | | | 001-099 |
| 0004 | 24 | GK | | | 1-0 | 34-33-21 | D00217B | J04 | | | D00217B | J06 | | | 115-199 |
| 0005 | 24 | GK | | | 0-7 | 34-33-21 | D00217B | F02 | | | D00217B | F03 | | | 001-099 |
| 0005 | 24 | GK | | | 1-0 | 34-33-21 | D00217B | F02 | | | D00217B | F03 | | | 115-199 |
| 0006 | 24 | GK | | | 0-7 | 34-33-21 | D00217B | C05 | | | D00217B | B06 | | | 001-099 |
| 0006 | 24 | GK | | | 1-0 | 34-33-21 | D00217B | C05 | | | D00217B | B06 | | | 115-199 |
| 0007 | 24 | GK | | | 3-6 | 34-33-21 | D00217B | G05 | | | D40598J | 24 | | | 001-099 |
| 0007 | 24 | GK | | | 3-0 | 34-33-21 | D00217B | G05 | | | D40598J | 24 | | | 115-199 |
| 0008 | 22 | GA | | | 3-10 | 34-33-21 | D00217B | F05 | | | GD02076 | DC.. | 2 | | 001-099 |
| 0008 | 22 | GA | | | 4-0 | 34-33-21 | D00217B | F05 | | | GD02076 | DC.. | 2 | | 115-199 |
| 0009 | 22 | GA | | | 3-10 | 34-33-21 | D00217B | F06 | | | GD02076 | DC.. | 2 | | 001-099 |
| 0009 | 22 | GA | | | 4-0 | 34-33-21 | D00217B | F06 | | | GD02076 | DC.. | 2 | | 115-199 |
| 0010 | 24 | GK | | | 4-6 | 34-33-21 | D00217B | F04 | | | D41379J | 44 | | | 001-099 |
| 0010 | 24 | GK | | | 4-0 | 34-33-21 | D00217B | F04 | | | D41379J | 44 | | | 115-199 |
| 0011 | 22 | GA | | | 4-6 | 22-12-21 | D00217B | K06 | | | D41379J | 37 | | | 001-099 |
| 0011 | 22 | GA | | | 4-0 | 22-12-21 | D00217B | K06 | | | D41379J | 37 | | | 115-199 |
| 0012 | 22 | GA | | | 3-2 | 22-24-21 | D03260B | A08 | | | D41379J | 20 | | | 001-099 |
| 0012 | 22 | GA | | | 3-0 | 22-24-21 | D03260B | A08 | | | D41379J | 20 | | | 115-199 |
| 0013 | 22 | GA | | | 3-10 | 74-31-21 | TB0184Y | A008 | BJ | | D41730J | 4 | | | 001-099 |
| 0013 | 22 | GA | | | 3-0 | 74-31-21 | D03260B | C10 | | | D41730J | 4 | | | 115-199 |
| 0014 | 22 | GA | | | 3-0 | 76-11-21 | D03260B | H08 | | | D41730J | 1 | | | 115-199 |
| 0015 | 22 | GA | | | 1-7 | 24-41-11 | D40710J | 2 | | | D41730J | 10 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 34

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | | 286N1284 | | | | E5-2 SHELF (continued) | | | | | | | | | |
| 0015 | 22 | GA | | | 2-0 | 24-41-11 | D40710J | | 2 | | D41730J | 10 | | | 115-199 |
| 0016 | 22 | GA | | | 2-0 | 27-51-21 | D42095J | | 15 | | D41694J | 17 | | | 001-099 |
| 0016 | 22 | GA | | | 3-0 | 27-51-21 | D42095J | | 15 | | D41694J | 17 | | | 115-199 |
| 0017 | 22 | GA | | | 2-8 | 24-21-21 | D02070B | | A15 | | D40492J | 1 | | | 001-099 |
| 0017 | 22 | GA | | | 3-0 | 24-21-21 | D02070B | | A15 | | D40492J | 1 | | | 115-199 |
| 0018 | 22 | GA | | | 2-8 | 24-21-21 | D02070B | | B15 | | D40492J | 2 | | | 001-099 |
| 0018 | 22 | GA | | | 3-0 | 24-21-21 | D02070B | | B15 | | D40492J | 2 | | | 115-199 |
| 0019 | 22 | GA | | | 2-8 | 24-21-21 | D02070B | | C15 | | D40492J | 4 | | | 001-099 |
| 0019 | 22 | GA | | | 3-0 | 24-21-21 | D02070B | | C15 | | D40492J | 4 | | | 115-199 |
| 0020 | 24 | GK | | | 2-6 | 24-22-11 | D02070A | | A06 | | D40492J | 3 | | | 001-099 |
| 0020 | 24 | GK | | | 3-0 | 24-22-11 | D02070A | | A06 | | D40492J | 3 | | | 115-199 |
| 0021 | 22 | GA | | | 3-2 | 22-12-21 | D03260B | | E13 | | D41379J | 14 | | | 001-099 |
| 0021 | 22 | GA | | | 3-0 | 22-12-21 | D03260B | | E13 | | D41379J | 14 | | | 115-199 |
| 0022 | 22 | GA | | | 3-2 | 22-12-21 | D03260B | | F13 | | D41379J | 15 | | | 001-099 |
| 0022 | 22 | GA | | | 3-0 | 22-12-21 | D03260B | | F13 | | D41379J | 15 | | | 115-199 |
| 0023 | 22 | GA | | | 3-1 | 27-41-21 | D03260B | | C08 | | D41883J | 9 | | | 001-099 |
| 0023 | 22 | GA | | | 3-0 | 27-41-21 | D03260B | | C08 | | D41883J | 9 | | | 115-199 |
| 0024 | 22 | GA | | | 2-6 | 24-11-21 | D02070B | | A03 | | D40908J | 9 | | | 001-099 |
| 0024 | 22 | GA | | | 4-0 | 24-11-21 | D02070B | | A03 | | D40908J | 9 | | | 115-199 |
| 0025 | 22 | GA | | | 2-10 | 24-11-21 | D02070B | | D15 | | GD02071 | DC.. | 2 | | 001-099 |
| 0025 | 22 | GA | | | 3-0 | 24-11-21 | D02070B | | D15 | | GD02071 | DC.. | 2 | | 115-199 |
| 0026 | 22 | GA | | | 2-10 | 24-11-21 | D02070B | | A08 | | GD02071 | ST.. | 2 | | 001-099 |
| 0026 | 22 | GA | | | 3-0 | 24-11-21 | D02070B | | A08 | | GD02071 | ST.. | 2 | | 115-199 |
| 0027 | 20 | GA | | | 3-11 | 24-11-21 | D40600J | | 23 | | TB0184Y | C008 | BJ | | 001-099 |
| 0027 | 20 | GA | | | 5-0 | 24-11-21 | D40600J | | 23 | | TB0184Y | C008 | BJ | | 115-199 |
| 0028 | 22 | GA | | | 2-7 | 24-11-21 | D02070A | | D02 | | TB0184Y | C008 | BJ | | 001-099 |
| 0028 | 22 | GA | | | 5-0 | 24-11-21 | D02070A | | D02 | | TB0184Y | C008 | BJ | | 115-199 |
| 0029 | 20 | GA | | | 2-0 | 24-11-21 | D40398J | | 16 | | TB0184Y | C008 | BJ | | 001-099 |
| 0029 | 20 | GA | | | 3-0 | 24-11-21 | D40398J | | 16 | | TB0184Y | C008 | BJ | | 115-199 |
| 0030 | 24 | GK | | | 2-5 | 24-11-21 | D02070A | | C04 | | D40598J | 39 | | | 001-099 |
| 0030 | 22 | GA | | | 3-0 | 24-11-21 | D02070A | | C04 | | D40598J | 39 | | | 115-199 |
| 0031 | 22 | GA | | | 3-11 | 27-51-21 | D42095J | | 16 | | D41883J | 14 | | | 001-099 |
| 0031 | 22 | GA | | | 5-0 | 27-51-21 | D42095J | | 16 | | D41883J | 14 | | | 115-199 |
| 0032 | 24 | GK | | | 2-5 | 24-11-21 | D02070A | | D10 | | D40598J | 33 | | | 001-099 |
| 0032 | 24 | GK | | | 3-0 | 24-11-21 | D02070A | | D10 | | D40598J | 33 | | | 115-199 |
| 0033 | 24 | GK | | | 2-6 | 24-11-21 | D02070B | | D08 | | D40598J | 2 | | | 001-099 |
| 0033 | 24 | GK | | | 3-0 | 24-11-21 | D02070B | | D08 | | D40598J | 2 | | | 115-199 |
| 0034 | 22 | GA | | | 3-11 | 27-51-21 | D42095J | | 17 | | D41883J | 13 | | | 001-099 |
| 0034 | 22 | GA | | | 5-0 | 27-51-21 | D42095J | | 17 | | D41883J | 13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 35

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 0035 | 24 | | GK | | 2-3 | 24-11-21 | D02070A | | C06 | | D40398J | | 8 | | 001-099 |
| 0035 | 24 | | GK | | 2-0 | 24-11-21 | D02070A | | C06 | | D40398J | | 8 | | 115-199 |
| 0036 | 22 | | GA | | 1-8 | 22-21-11 | D40598J | | 23 | | D41461J | | 4 | | 001-099 |
| 0036 | 22 | | GA | | 3-0 | 22-21-11 | D40598J | | 23 | | D41461J | | 4 | | 115-199 |
| 0037 | 22 | | GA | | 2-10 | 22-21-11 | D40600J | | 15 | | D41461J | | 5 | | 001-099 |
| 0037 | 22 | | GA | | 3-0 | 22-21-11 | D40600J | | 15 | | D41461J | | 5 | | 115-199 |
| 0038 | 22 | | GA | | 2-10 | 22-21-11 | D40600J | | 16 | | D41461J | | 6 | | 001-099 |
| 0038 | 22 | | GA | | 3-0 | 22-21-11 | D40600J | | 16 | | D41461J | | 6 | | 115-199 |
| 0039 | 24 | | GK | | 2-9 | 32-41-11 | D02744B | | D15 | | D41461J | | 55 | | 001-099 |
| 0041 | 24 | | GK | | 3-0 | 24-11-21 | D40598J | | 14 | | D02070A | | D13 | | ALL |
| 0062 | 18 | | GA | | 2-2 | 24-22-21 | SM00008 | | | WI | D40492J | | 8 | | 001-099 |
| 0062 | 18 | | GA | | 5-0 | 24-22-21 | SM00008 | | | WI | D40492J | | 8 | | 115-199 |
| 0063 | 24 | | GK | | 2-6 | 24-22-21 | D02070A | | D06 | | D40492J | | 23 | | 001-099 |
| 0063 | 24 | | GK | | 3-0 | 24-22-21 | D02070A | | D06 | | D40492J | | 23 | | 115-199 |
| 0064 | 22 | | GA | | 2-6 | 24-22-21 | D02070A | | C01 | | D40492J | | 24 | | 001-099 |
| 0064 | 22 | | GA | | 3-0 | 24-22-21 | D02070A | | C01 | | D40492J | | 24 | | 115-199 |
| 0065 | 22 | | GA | | 2-6 | 24-22-21 | D02070A | | B01 | | D40492J | | 25 | | 001-099 |
| 0065 | 22 | | GA | | 3-0 | 24-22-21 | D02070A | | B01 | | D40492J | | 25 | | 115-199 |
| 0066 | 22 | | GA | | 2-5 | 24-22-21 | D02070A | | C05 | | D40598J | | 38 | | 001-099 |
| 0066 | 22 | | GA | | 3-0 | 24-22-21 | D02070A | | C05 | | D40598J | | 38 | | 115-199 |
| 0067 | 22 | | GA | | 2-8 | 24-22-21 | D02070A | | A07 | | GD02071 | | DC.. | 2 | 001-099 |
| 0067 | 22 | | GA | | 3-0 | 24-22-21 | D02070A | | A07 | | GD02071 | | DC.. | 2 | 115-199 |
| 0068 | 22 | | GA | | 2-8 | 24-22-21 | D02070A | | A11 | | GD02071 | | DC.. | 2 | 001-099 |
| 0068 | 22 | | GA | | 3-0 | 24-22-21 | D02070A | | A11 | | GD02071 | | DC.. | 2 | 115-199 |
| 0069 | 24 | | GK | | 2-5 | 24-22-21 | D02070A | | B05 | | D40598J | | 10 | | 001-099 |
| 0069 | 24 | | GK | | 3-0 | 24-22-21 | D02070A | | B05 | | D40598J | | 10 | | 115-199 |
| 0070 | 22 | | GA | | 2-8 | 24-22-21 | D02070B | | D02 | | TB0184Y | | C011 | BJ | 001-099 |
| 0070 | 22 | | GA | | 3-0 | 24-22-21 | D02070B | | D02 | | TB0184Y | | C011 | BJ | 115-199 |
| 0071 | 22 | | GA | | 2-5 | 24-22-21 | D02070A | | C02 | | D40598J | | 13 | | 001-099 |
| 0071 | 22 | | GA | | 3-0 | 24-22-21 | D02070A | | C02 | | D40598J | | 13 | | 115-199 |
| 0072 | 24 | | GK | | 2-5 | 24-22-21 | D02070A | | A05 | | D40598J | | 12 | | 001-003 |
| 0072 | 24 | | GK | | 3-0 | 24-22-21 | D02070A | | A05 | | D40598J | | 12 | | 115-199 |
| 0073 | 24 | | GK | | 2-5 | 24-22-21 | D02070A | | D04 | | D40598J | | 11 | | 001-003 |
| 0073 | 24 | | GK | | 3-0 | 24-22-21 | D02070A | | D04 | | D40598J | | 11 | | 115-199 |
| 0074 | 24 | | GK | | 2-7 | 24-22-22 | D02070A | | A01 | | TB0184Y | | A012 | BJ | 001-099 |
| 0074 | 24 | | GK | | 5-0 | 24-22-22 | D02070A | | A01 | | TB0184Y | | A012 | BJ | 115-199 |
| 0075 | 24 | | GK | | 2-10 | 24-28-21 | D41461J | | 1 | | TB0184Y | | A003 | BJ | 001-099 |
| 0075 | 24 | | GK | | 4-0 | 24-28-21 | D41461J | | 1 | | TB0184Y | | A003 | BJ | 115-199 |
| 0076 | 24 | | GK | | 2-7 | 24-28-21 | D02070A | | A10 | | TB0184Y | | A003 | BJ | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 36

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 0076 | 24 | | GK | | 3-0 | 24-28-21 | D02070A | A10 | | | TB0184Y | A003 | BJ | | 115-199 |
| 0077 | 24 | | GK | | 2-7 | 24-28-21 | D02070A | B02 | | | TB0184Y | A003 | BJ | | 001-099 |
| 0077 | 24 | | GK | | 3-0 | 24-28-21 | D02070A | B02 | | | TB0184Y | A003 | BJ | | 115-199 |
| 0079 | 24 | | GK | | 3-11 | 24-22-22 | D41883J | 37 | | | TB0184Y | A012 | BJ | | 001-099 |
| 0079 | 24 | | GK | | 5-0 | 24-22-22 | D41883J | 37 | | | TB0184Y | A012 | BJ | | 115-199 |
| 0080 | 24 | | GK | | 3-11 | 24-22-22 | D41883J | 38 | | | TB0184Y | A012 | BJ | | 001-099 |
| 0080 | 24 | | GK | | 5-0 | 24-22-22 | D41883J | 38 | | | TB0184Y | A012 | BJ | | 115-199 |
| 0081 | 24 | | GK | | 3-11 | 24-22-22 | D41883J | 39 | | | TB0184Y | A012 | BJ | | 001-099 |
| 0081 | 24 | | GK | | 5-0 | 24-22-22 | D41883J | 39 | | | TB0184Y | A012 | BJ | | 115-199 |
| 0089 | 24 | | GK | | 2-5 | 24-22-22 | D02070A | D08 | | | D40598J | 17 | | | 001-099 |
| 0089 | 24 | | GK | | 3-0 | 24-22-22 | D02070A | D08 | | | D40598J | 17 | | | 115-199 |
| 0090 | 22 | | GA | | 2-6 | 24-22-22 | D02070A | A08 | | | D40492J | 27 | | | 001-099 |
| 0090 | 22 | | GA | | 3-0 | 24-22-22 | D02070A | A08 | | | D40492J | 27 | | | 115-199 |
| 0091 | 22 | | GA | | 2-6 | 24-22-22 | D02070A | C07 | | | D40492J | 15 | | | 001-099 |
| 0091 | 22 | | GA | | 3-0 | 24-22-22 | D02070A | C07 | | | D40492J | 15 | | | 115-199 |
| 0092 | 18 | | GA | | 2-2 | 24-22-22 | SM00007 | | WI | | D40492J | 6 | | | 001-099 |
| 0092 | 18 | | GA | | 3-0 | 24-22-22 | SM00007 | | WI | | D40492J | 6 | | | 115-199 |
| 0093 | 24 | | GK | | 2-6 | 24-22-22 | D02070A | D05 | | | D40492J | 21 | | | 001-099 |
| 0093 | 24 | | GK | | 3-0 | 24-22-22 | D02070A | D05 | | | D40492J | 21 | | | 115-199 |
| 0094 | 22 | | GA | | 2-6 | 24-22-22 | D02070A | C08 | | | D40492J | 22 | | | 001-099 |
| 0094 | 22 | | GA | | 3-0 | 24-22-22 | D02070A | C08 | | | D40492J | 22 | | | 115-199 |
| 0095 | 24 | | GK | | 2-6 | 24-27-21 | D02070A | D07 | | | D40894J | 14 | | | 001-099 |
| 0095 | 24 | | GK | | 3-0 | 24-27-21 | D02070A | D07 | | | D40894J | 14 | | | 115-199 |
| 0099 | 24 | | GK | | 3-0 | 27-51-11 | D03260B | G06 | | | D41694J | 3 | | | ALL |
| 0100 | 24 | | GK | | 3-0 | 27-51-11 | D03260B | F06 | | | D41694J | 4 | | | ALL |
| 0101 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | A09 | | | D42095J | 10 | | | ALL |
| 0102 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | B09 | | | D42095J | 9 | | | ALL |
| 0103 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | B10 | | | D42095J | 1 | | | ALL |
| 0104 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | C10 | | | D42095J | 2 | | | ALL |
| 0105 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | D10 | | | D42095J | 3 | | | ALL |
| 0106 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | E10 | | | D42095J | 4 | | | ALL |
| 0107 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | F10 | | | D42095J | 5 | | | ALL |
| 0108 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | G10 | | | D42095J | 6 | | | ALL |
| 0109 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | K09 | | | D42095J | 7 | | | 115-199 |
| 0110 | 24 | | GK | | 3-0 | 27-51-11 | D03260A | A10 | | | D42095J | 19 | | | ALL |
| 0111 | 20 | | GA | | 1-10 | 27-21-11 | D40007J | 1 | | | D40600J | 27 | | | 001-009 |
| 0111 | 20 | | GA | | 1-10 | 27-21-11 | D40007J | 1 | | | SM00022 | | WI | | 010-099 |
| 0112 | 20 | | GA | | 1-10 | 27-21-11 | D40007J | 2 | | | D40600J | 28 | | | 001-009 |
| 0112 | 20 | | GA | | 1-10 | 27-21-11 | D40007J | 2 | | | SM00023 | | WI | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 37

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 0113 | 24 | | GK | | 3-0 | 27-32-21 | D03260B | E10 | | | D41379J | 8 | | | 115-199 |
| 0117 | 24 | | GK | | 3-0 | 27-32-21 | D03260B | H10 | | | D41379J | 12 | | | 115-199 |
| 0118 | 24 | | GK | | 2-9 | 27-81-11 | D03260A | D03 | | | D40710J | 4 | | | 001-099 |
| 0118 | 24 | | GK | | 3-0 | 27-81-11 | D03260A | D03 | | | D40710J | 4 | | | 115-199 |
| 0119 | 24 | | GK | | 2-9 | 27-81-11 | D03260A | H03 | | | D40710J | 5 | | | 001-099 |
| 0119 | 24 | | GK | | 3-0 | 27-81-11 | D03260A | H03 | | | D40710J | 5 | | | 115-199 |
| 0120 | 24 | | GK | | 2-9 | 27-81-11 | D03260A | F03 | | | D40710J | 3 | | | 001-099 |
| 0120 | 24 | | GK | | 3-0 | 27-81-11 | D03260A | F03 | | | D40710J | 3 | | | 115-199 |
| 0121 | 24 | | GK | | 3-0 | 27-81-11 | D03260B | J06 | | | D41694J | 2 | | | ALL |
| 0122 | 24 | | GK | | 3-0 | 27-81-11 | D03260B | H06 | | | D41694J | 1 | | | ALL |
| 0123 | 22 | | GA | | 3-0 | 32-42-12 | D02744A | A10 | | | D42510J | 7 | | | 001-099 |
| 0124 | 22 | | GA | | 3-0 | 32-42-12 | D02744A | B10 | | | D42510J | 8 | | | 001-099 |
| 0125 | 22 | | GA | | 3-0 | 32-42-12 | D42516J | | | DB | GD02071 | ST.. | 2 | | 001-099 |
| 0127 | 22 | | GA | | 2-7 | 32-42-12 | D02744A | C07 | | | D42516J | 10 | | | 001-099 |
| 0128 | 22 | | GA | | 2-9 | 32-42-12 | D02744B | A10 | | | D42516J | 11 | | | 001-099 |
| 0129 | 22 | | GA | | 2-7 | 32-42-12 | D02744A | B08 | | | D42516J | 12 | | | 001-099 |
| 0130 | 22 | | GA | | 2-4 | 32-42-12 | D02744B | D04 | | | TB0184Y | C005 | BJ | | 001-099 |
| 0131 | 22 | | GA | | 2-10 | 32-42-12 | TB0184Y | C005 | BJ | | D42516J | 13 | | | 001-099 |
| 0132 | 22 | | GA | | 2-9 | 32-42-12 | D02744B | B08 | | | D42516J | 14 | | | 001-099 |
| 0133 | 22 | | GA | | 2-9 | 32-42-12 | D02744B | A09 | | | D42516J | 15 | | | 001-099 |
| 0134 | 20 | | GA | | 2-3 | 21-31-21 | D41694J | 9 | | | TB0184Y | A011 | BJ | | 001-099 |
| 0134 | 20 | | GA | | 4-0 | 21-31-21 | D41694J | 9 | | | TB0184Y | A011 | BJ | | 115-199 |
| 0135 | 22 | | GA | | 3-4 | 21-31-21 | D02342A | A15 | | | TB0184Y | A011 | BJ | | 001-099 |
| 0135 | 22 | | GA | | 3-0 | 21-31-21 | D02342A | A15 | | | TB0184Y | A011 | BJ | | 115-199 |
| 0136 | 22 | | GA | | 3-1 | 21-31-21 | D02342A | D15 | | | GD02074 | AC.. | 2 | | 001-099 |
| 0136 | 22 | | GA | | 3-0 | 21-31-21 | D02342A | D15 | | | GD02074 | AC.. | 2 | | 115-199 |
| 0137 | 24 | | GK | | 3-3 | 21-31-21 | D41694J | 26 | | | D02342A | A02 | | | 001-099 |
| 0137 | 24 | | GK | | 3-0 | 21-31-21 | D41694J | 26 | | | D02342A | A02 | | | 115-199 |
| 0138 | 24 | | GK | | 3-3 | 21-31-21 | D41694J | 29 | | | D02342A | D02 | | | 001-099 |
| 0138 | 24 | | GK | | 3-0 | 21-31-21 | D41694J | 29 | | | D02342A | D02 | | | 115-199 |
| 0139 | 22 | | GA | | 3-1 | 21-31-21 | D02342A | C12 | | | GD02074 | DC.. | 2 | | 001-099 |
| 0139 | 22 | | GA | | 3-0 | 21-31-21 | D02342A | C12 | | | GD02074 | DC.. | 2 | | 115-199 |
| 0140 | 22 | | GA | | 3-1 | 21-31-21 | D02342A | | | FN | GD02074 | ST.. | 2 | | 001-099 |
| 0140 | 22 | | GA | | 3-0 | 21-31-21 | D02342A | | | FN | GD02074 | ST.. | 2 | | 115-199 |
| 0141 | 24 | | GK | | 2-6 | 21-31-21 | D02342A | B02 | | | D41327J | 4 | | | 001-099 |
| 0141 | 24 | | GK | | 2-0 | 21-31-21 | D02342A | B02 | | | D41327J | 4 | | | 115-199 |
| 0142 | 24 | | GK | | 3-6 | 21-31-21 | D02342A | B08 | | | D42412J | 6 | | | 001-099 |
| 0142 | 24 | | GK | | 2-0 | 21-31-21 | D02342A | B08 | | | D40598J | 3 | | | 115-199 |
| 0143 | 20 | | GA | | 3-1 | 21-31-21 | D02342A | | | FL | GD02074 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 38

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | |
|------------------------|-------------|----|----|------|------------------------|---------|---------|------|--------|-------|---------|------|--------|-------------|--|
| | GA | CO | TY | | Equip | Term | | Type | Splice | Equip | Term | Type | Splice | | |
| W1284 | 286N1284 | | | | E5-2 SHELF (continued) | | | | | | | | | | |
| 0143 | 20 | | GA | 3-0 | 21-31-21 | D02342A | | | | FL | GD02074 | ST.. | 2 | 115-199 | |
| 0144 | 20 | | GA | 3-0 | 21-31-21 | TB0184Y | A011 | BJ | | | D40182J | 27 | | 001-099 | |
| 0144 | 20 | | GA | 4-0 | 21-31-21 | TB0184Y | A011 | BJ | | | D40182J | 27 | | 115-199 | |
| 0156 | 24 | | GK | 3-2 | 27-58-31 | D41379J | | 39 | | | D03260B | G11 | | 001-099 | |
| 0156 | 24 | | GK | 3-0 | 27-58-31 | D41379J | | 39 | | | D03260B | G11 | | 115-199 | |
| 0158 | 24 | | GK | 3-2 | 27-58-31 | D03260B | | D11 | | | D41379J | 16 | | 001-099 | |
| 0158 | 24 | | GK | 3-0 | 27-58-31 | D03260B | | D11 | | | D41379J | 16 | | 115-199 | |
| 0159 | 24 | | GK | 3-2 | 27-58-31 | D03260B | | E11 | | | D41379J | 40 | | 001-099 | |
| 0159 | 24 | | GK | 3-0 | 27-58-31 | D03260B | | E11 | | | D41379J | 40 | | 115-199 | |
| 0163 | 24 | | GK | 0-7 | 27-58-31 | D03260A | | B11 | | | D03260A | B08 | | 001-099 | |
| 0163 | 22 | | GA | 1-0 | 27-58-31 | D03260A | | B11 | | | D03260A | B08 | | 115-199 | |
| 0164 | 24 | | GK | 0-7 | 27-58-31 | D03260A | | K10 | | | D03260A | K08 | | 001-099 | |
| 0164 | 22 | | GA | 1-0 | 27-58-31 | D03260A | | K10 | | | D03260A | K08 | | 115-199 | |
| 0165 | 22 | | GA | 2-8 | 27-58-31 | D03260A | | K15 | | | GD02073 | ST.. | 2 | 001-099 | |
| 0165 | 22 | | GA | 3-0 | 27-58-31 | D03260A | | K15 | | | GD02073 | ST.. | 2 | 115-199 | |
| 0166 | 22 | | GA | 3-5 | 32-42-12 | D40190J | | 1 | | | D02744B | A08 | | 001-099 | |
| 0167 | 22 | | GA | 3-5 | 32-42-12 | D40190J | | 2 | | | D02744B | C08 | | 001-099 | |
| 0168 | 22 | | GA | 2-2 | 32-42-12 | D40492J | | 7 | | | D02744A | A08 | | 001-099 | |
| 0169 | 22 | | GA | 2-2 | 32-42-12 | D40492J | | 26 | | | D02744A | C08 | | 001-099 | |
| 0170 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 1 | | | D02744B | C14 | | 001-099 | |
| 0171 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 10 | | | D02744B | D12 | | 001-099 | |
| 0172 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 2 | | | D02744B | D07 | | 001-099 | |
| 0173 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 3 | | | D02744B | D08 | | 001-099 | |
| 0174 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 4 | | | D02744B | D09 | | 001-099 | |
| 0175 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 5 | | | D02744B | D10 | | 001-099 | |
| 0176 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 6 | | | D02744B | D11 | | 001-099 | |
| 0177 | 22 | | GA | 3-3 | 32-42-12 | D40219J | | 7 | | | TB0184Y | A005 | BJ | 001-099 | |
| 0178 | 22 | | GA | 3-3 | 32-42-12 | D40219J | | 8 | | | TB0184Y | C005 | BJ | 001-099 | |
| 0179 | 22 | | GA | 2-4 | 32-42-12 | TB0184Y | A005 | BJ | | | D02744B | C03 | | 001-099 | |
| 0180 | 22 | | GA | 2-4 | 32-42-12 | TB0184Y | A005 | BJ | | | D02744B | C12 | | 001-099 | |
| 0181 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 11 | | | D02744B | C09 | | 001-099 | |
| 0182 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 13 | | | D02744B | C10 | | 001-099 | |
| 0183 | 22 | | GA | 3-2 | 32-42-12 | D40219J | | 12 | | | D02744B | C07 | | 001-099 | |
| 0184 | 22 | | GA | 3-0 | 32-42-12 | D40219J | | 9 | | | D02744A | D07 | | 001-099 | |
| 0185 | 22 | | GA | 2-6 | 32-42-12 | D42412J | | 3 | | | D02744B | A02 | | 001-099 | |
| 0186 | 22 | | GA | 2-5 | 32-42-12 | D42412J | | 2 | | | TB0184Y | A006 | BJ | 001-099 | |
| 0187 | 22 | | GA | 2-6 | 32-42-12 | D42412J | | 1 | | | D02744B | D06 | | 001-099 | |
| 0188 | 22 | | GA | 3-10 | 32-42-12 | D42414J | | 3 | | | D02744B | A07 | | 001-099 | |
| 0189 | 22 | | GA | 2-4 | 32-42-12 | TB0184Y | A006 | BJ | | | D02744B | B09 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 39

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 0190 | 22 | | GA | | 3-11 | 32-42-12 | D42414J | | 2 | | TB0184Y | A006 | BJ | | 001-099 |
| 0191 | 22 | | GA | | 3-10 | 32-42-12 | D42414J | | 1 | | D02744B | A04 | | | 001-099 |
| 0192 | 22 | | GA | | 2-6 | 32-42-12 | D42412J | | 4 | | D02744B | C11 | | | 001-099 |
| 0193 | 22 | | GA | | 2-4 | 32-42-12 | D42412J | | 5 | | D02744A | A07 | | | 001-099 |
| 0194 | 22 | | GA | | 2-8 | 27-81-11 | D03260A | | F04 | | GD02073 | AC.. | 2 | | 001-099 |
| 0194 | 22 | | GA | | 3-0 | 27-81-11 | D03260A | | F04 | | GD02073 | AC.. | 2 | | 115-199 |
| 0195 | 12 | | GA | | 2-7 | 27-81-11 | D03260C | | 8 | | GD03035 | DC.. | E | | 001-099 |
| 0195 | 12 | | GA | | 3-0 | 27-81-11 | D03260C | | 8 | | GD03035 | DC.. | E | | 115-199 |
| 0196 | 22 | | GA | | 2-8 | 27-81-11 | D03260A | | D04 | | GD02073 | AC.. | 2 | | 001-099 |
| 0196 | 22 | | GA | | 3-0 | 27-81-11 | D03260A | | D04 | | GD02073 | AC.. | 2 | | 115-199 |
| 0197 | 20 | | GA | | 3-1 | 21-31-21 | D02342A | | | FM | GD02074 | ST.. | 2 | | 001-099 |
| 0197 | 20 | | GA | | 3-0 | 21-31-21 | D02342A | | | FM | GD02074 | ST.. | 2 | | 115-199 |
| 0198 | 22 | | GA | | 3-1 | 21-31-21 | D02342A | | B12 | | GD02074 | ST.. | 2 | | 001-099 |
| 0198 | 22 | | GA | | 3-0 | 21-31-21 | D02342A | | B12 | | GD02074 | ST.. | 2 | | 115-199 |
| 0200 | 22 | | GA | | 2-10 | 33-16-51 | D41461J | | 7 | | D40600J | | 6 | | 001-099 |
| 0200 | 22 | | GA | | 3-0 | 33-16-51 | D41461J | | 7 | | D40600J | | 6 | | 115-199 |
| 0201 | 24 | | GK | | 2-4 | 24-11-11 | D40908J | | 2 | | D02070A | A02 | | | 001-099 |
| 0201 | 24 | | GK | | 4-0 | 24-11-11 | D40908J | | 2 | | D02070A | A02 | | | 115-199 |
| 0205 | 24 | | GK | | 3-11 | 27-51-31 | D41883J | | 12 | | D42095J | | 14 | | 001-099 |
| 0205 | 22 | | GA | | 5-0 | 27-51-31 | D41883J | | 12 | | D42095J | | 14 | | 115-199 |
| 0207 | 22 | | GA | | 2-7 | 24-22-21 | D02070A | | A03 | | TB0184Y | C011 | BJ | | 001-099 |
| 0207 | 22 | | GA | | 3-0 | 24-22-21 | D02070A | | A03 | | TB0184Y | C011 | BJ | | 115-199 |
| 0208 | 22 | | GA | | 3-0 | 24-22-21 | D40598J | | 9 | | TB0184Y | C011 | BJ | | ALL |
| 0209 | 22 | | GA | | 2-10 | 24-22-21 | D02070B | | A07 | | GD02071 | DC.. | 2 | | 001-099 |
| 0209 | 22 | | GA | | 3-0 | 24-22-21 | D02070B | | A07 | | GD02071 | DC.. | 2 | | 115-199 |
| 0210 | 24 | | GK | | 3-1 | 21-25-11 | D03260B | | A10 | | D40600J | | 2 | | 001-099 |
| 0210 | 24 | | GK | | 4-0 | 21-25-11 | D03260B | | A10 | | D40600J | | 2 | | 115-199 |
| 0214 | 24 | | GK | | 0-7 | 21-31-21 | D02342A | | D11 | | D02342A | D10 | | | 001-003, 005, 007-008 |
| 0214 | 24 | | GK | | 0-7 | 21-31-21 | D02342A | | D11 | | D02342A | D12 | | | 004, 006 |
| 0214 | 24 | | GK | | 3-4 | 21-31-21 | D02342A | | D10 | | TB0184X | B009 | BJ | | 009-099 |
| 0214 | 24 | | GK | | 1-0 | 21-31-21 | D02342A | | D11 | | D02342A | D10 | | | 115-199 |
| 0215 | 24 | | GK | | 0-7 | 21-31-21 | D02342A | | B10 | | D02342A | B09 | | | 001-099 |
| 0215 | 24 | | GK | | 1-0 | 21-31-21 | D02342A | | B10 | | D02342A | B09 | | | 115-199 |
| 0217 | 20 | | GA | | 1-6 | 22-12-21 | D41379J | | | AD | GD02072 | ST.. | 2 | | 001-099 |
| 0217 | 20 | | GA | | 1-6 | 22-12-21 | D41379J | | | FO | GD02072 | ST.. | 2 | | 115-199 |
| 0224 | 22 | | GA | | 0-6 | 24-22-22 | D02070A | | D15 | | SM00007 | | WI | | ALL |
| 0225 | 22 | | GA | | 0-6 | 24-22-21 | D02070A | | C15 | | SM00008 | | WI | | ALL |
| 0240 | 24 | | GK | | 0-7 | 21-31-21 | TB0184X | | B009 | BJ | TB0184X | A009 | BJ | | 009-099 |
| 0252 | 22 | | GA | | 3-10 | 74-31-21 | D41730J | | 2 | | TB0184Y | A008 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 40

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | | 286N1284 | | | | E5-2 SHELF (continued) | | | | | | | | | |
| 0253 | 22 | GA | | | 3-1 | 74-31-21 | TB0184Y | A008 | BJ | | D03260B | C10 | | | 001-099 |
| 0255 | 22 | GA | | | 3-0 | 76-11-21 | D03260B | H08 | | | D41730J | 3 | | | 001-099 |
| 0278 | 24 | GK | | | 3-4 | 21-31-21 | TB0184X | C009 | BJ | | D02342A | D12 | | | 009-099 |
| 0283 | 24 | GK | | | 3-4 | 21-31-21 | TB0184X | A009 | BJ | | D02342A | D11 | | | 009-099 |
| 0298 | 20 | GA | | | 0-7 | 27-21-11 | D40600J | 27 | | | SM00022 | | WI | | 010-099 |
| 0299 | 20 | GA | | | 0-7 | 27-21-11 | D40600J | 28 | | | SM00023 | | WI | | 010-099 |
| 0300 | 20 | GA | | | 4-0 | 31-31-61 | D41379J | 9 | | | SM00022 | | WI | | 010-099 |
| 0301 | 22 | GA | | | 2-8 | 32-42-11 | D41461J | 32 | | | D02744A | D01 | | | 001-099 |
| 0302 | 22 | GA | | | 2-9 | 32-42-11 | D41461J | 31 | | | D02744B | D01 | | | 001-099 |
| 0303 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | C02 | | | GD02075 | DC.. | 2 | | 001-099 |
| 0304 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | C15 | | | GD02075 | DC.. | 2 | | 001-099 |
| 0305 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | C13 | | | GD02075 | ST.. | 2 | | 001-099 |
| 0306 | 22 | GA | | | 3-5 | 32-42-11 | D40190J | 6 | | | D02744B | C05 | | | 001-099 |
| 0307 | 22 | GA | | | 3-5 | 32-42-11 | D40190J | 7 | | | D02744B | C01 | | | 001-099 |
| 0308 | 22 | GA | | | 3-5 | 32-42-11 | D40190J | 8 | | | D02744B | A11 | | | 001-099 |
| 0309 | 22 | GA | | | 3-5 | 32-42-11 | D40190J | 9 | | | D02744B | D05 | | | 001-099 |
| 0311 | 22 | GA | | | 3-3 | 32-42-11 | D40190J | 10 | | | D02744A | C05 | | | 001-099 |
| 0312 | 22 | GA | | | 3-8 | 32-42-11 | D40600J | 7 | | | D02744A | D05 | | | 001-099 |
| 0313 | 22 | GA | | | 3-8 | 32-42-11 | D40600J | 8 | | | D02744A | C01 | | | 001-099 |
| 0314 | 22 | GA | | | 3-8 | 32-42-11 | D40600J | 9 | | | D02744A | D06 | | | 001-099 |
| 0315 | 22 | GA | | | 3-8 | 32-42-11 | D40600J | 10 | | | D02744A | C03 | | | 001-099 |
| 0317 | 22 | GA | | | 3-8 | 32-42-11 | D40600J | 11 | | | D02744A | C11 | | | 001-099 |
| 0318 | 22 | GA | | | 2-11 | 32-42-11 | D02744A | C15 | | | GD02075 | DC.. | 2 | | 001-099 |
| 0319 | 22 | GA | | | 2-11 | 32-42-11 | D02744A | C06 | | | GD02075 | DC.. | 2 | | 001-099 |
| 0320 | 22 | GA | | | 2-8 | 32-42-11 | D41461J | 33 | | | D02744A | D03 | | | 001-099 |
| 0321 | 22 | GA | | | 2-11 | 32-42-11 | D02744A | C04 | | | GD02075 | DC.. | 2 | | 001-099 |
| 0322 | 22 | GA | | | 2-11 | 32-42-11 | D02744A | C02 | | | GD02075 | DC.. | 2 | | 001-099 |
| 0323 | 22 | GA | | | 2-11 | 32-42-11 | D02744A | C13 | | | GD02075 | ST.. | 2 | | 001-099 |
| 0325 | 22 | GA | | | 3-0 | 32-42-11 | D02744A | A01 | | | D42510J | 10 | | | 001-099 |
| 0326 | 22 | GA | | | 3-0 | 32-42-11 | D02744A | A03 | | | D42510J | 9 | | | 001-099 |
| 0327 | 22 | GA | | | 2-9 | 32-42-11 | D02744A | B15 | | | D42512J | 1 | | | 001-099 |
| 0328 | 22 | GA | | | 3-1 | 32-42-11 | D02744B | B01 | | | D42510J | 11 | | | 001-099 |
| 0329 | 22 | GA | | | 3-1 | 32-42-11 | D02744B | B03 | | | D42510J | 12 | | | 001-099 |
| 0330 | 22 | GA | | | 2-10 | 32-42-11 | D02744B | A15 | | | D42512J | 2 | | | 001-099 |
| 0331 | 22 | GA | | | 3-0 | 32-42-11 | D02744B | B15 | | | D42514J | 1 | | | 001-099 |
| 0332 | 22 | GA | | | 2-9 | 32-42-11 | D02744B | A01 | | | D42516J | 17 | | | 001-099 |
| 0333 | 22 | GA | | | 2-9 | 32-42-11 | D02744B | A03 | | | D42516J | 16 | | | 001-099 |
| 0334 | 22 | GA | | | 2-11 | 32-42-11 | D02744A | A15 | | | D42514J | 2 | | | 001-099 |
| 0335 | 22 | GA | | | 2-7 | 32-42-11 | D02744A | B01 | | | D42516J | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 41

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 0336 | 22 | | GA | | 2-7 | 32-42-11 | D02744A | B03 | | | D42516J | 19 | | | 001-099 |
| 0337 | 20 | | GA | | 2-11 | 32-42-11 | D42510J | | | AJ | GD02073 | ST.. | 2 | | 001-099 |
| 0338 | 20 | | GA | | 2-11 | 32-42-11 | D42510J | | | AK | GD02073 | ST.. | 2 | | 001-099 |
| 0339 | 20 | | GA | | 2-9 | 32-42-11 | D42520J | | | AN | GD02076 | ST.. | 2 | | 001-099 |
| 0340 | 20 | | GA | | 2-9 | 32-42-11 | D42520J | | | AL | GD02076 | ST.. | 2 | | 001-099 |
| 0341 | 20 | | GA | | 2-8 | 32-42-11 | D42518J | | | AP | GD02073 | ST.. | 2 | | 001-099 |
| 0342 | 20 | | GA | | 2-8 | 32-42-11 | D42518J | | | AM | GD02073 | ST.. | 2 | | 001-099 |
| 0343 | 20 | | GA | | 2-3 | 32-42-11 | D42516J | | | AQ | GD02076 | ST.. | 2 | | 001-099 |
| 0344 | 20 | | GA | | 2-3 | 32-42-11 | D42516J | | | AR | GD02076 | ST.. | 2 | | 001-099 |
| 0345 | 20 | | GA | | 4-0 | 31-31-61 | D41379J | 31 | | | SM00023 | | WI | | 010-099 |
| 0454 | 22 | | GA | | 3-8 | 32-44-11 | D40600J | 13 | | | D02744A | D15 | | | 001-099 |
| 1001 | 20 | | GT | BO | 2-0 | 27-21-11 | D40007J | 1 | | | D40600J | 27 | | | 115-199 |
| 1001Z | | | | BO | 0-0 | 27-21-11 | D40007J | DED | | | D40600J | DED | | | 115-199 |
| 1002 | 20 | | GT | CO | 2-0 | 27-21-11 | D40007J | 2 | | | D40600J | 28 | | | 115-199 |
| 1002Z | | | | CO | 0-0 | 27-21-11 | D40007J | DED | | | D40600J | DED | | | 115-199 |
| 2001B | 24 | | GL | AT | 3-0 | 27-51-11 | D03260B | B03 | | | D41694J | 7 | | | ALL |
| 2001R | 24 | | GL | AT | 0-0 | 27-51-11 | D03260B | A03 | | | D41694J | 8 | | | ALL |
| 2002B | 24 | | GL | AU | 3-0 | 27-81-11 | D03260B | F03 | | | D41694J | 5 | | | ALL |
| 2002R | 24 | | GL | AU | 0-0 | 27-81-11 | D03260B | E03 | | | D41694J | 6 | | | ALL |
| 2003B | 24 | | GL | AV | 3-0 | 27-32-21 | D03260B | D13 | | | D41379J | 7 | | | 115-199 |
| 2003R | 24 | | GL | AV | 0-0 | 27-32-21 | D03260B | C13 | | | D41379J | 13 | | | 115-199 |
| 2004B | 24 | | GL | AW | 2-3 | 24-11-21 | D02070A | B09 | | | D40398J | 10 | | | 001-099 |
| 2004B | 24 | | GL | AW | 2-0 | 24-11-21 | D02070A | B09 | | | D40398J | 10 | | | 115-199 |
| 2004R | 24 | | GL | AW | 0-0 | 24-11-21 | D02070A | A09 | | | D40398J | 19 | | | ALL |
| 2005B | 24 | | GL | BK | 2-3 | 24-11-21 | D02070A | D01 | | | D40398J | 21 | | | 001-099 |
| 2005B | 24 | | GL | BK | 2-0 | 24-11-21 | D02070A | D01 | | | D40398J | 21 | | | 115-199 |
| 2005R | 24 | | GL | BK | 0-0 | 24-11-21 | D02070A | D03 | | | D40398J | 11 | | | ALL |
| 2018B | 24 | | GL | CS | 2-6 | 21-31-21 | D02342A | C04 | | | D41327J | 6 | | | 001-099 |
| 2018B | 24 | | GL | CS | 2-0 | 21-31-21 | D02342A | C04 | | | D41327J | 6 | | | 115-199 |
| 2018R | 24 | | GL | CS | 0-0 | 21-31-21 | D02342A | C03 | | | D41327J | 5 | | | ALL |
| 2019B | 24 | | GL | CT | 2-6 | 21-31-21 | D02342A | D03 | | | D41327J | 8 | | | 001-099 |
| 2019B | 24 | | GL | CT | 2-0 | 21-31-21 | D02342A | D03 | | | D41327J | 8 | | | 115-199 |
| 2019R | 24 | | GL | CT | 0-0 | 21-31-21 | D02342A | D04 | | | D41327J | 7 | | | ALL |
| 2020B | 24 | | GL | CU | 2-5 | 21-31-21 | D02342A | A08 | | | D40598J | 4 | | | 001-099 |
| 2020B | 24 | | GL | CU | 2-0 | 21-31-21 | D02342A | A08 | | | D40598J | 4 | | | 115-199 |
| 2020R | 24 | | GL | CU | 0-0 | 21-31-21 | D02342A | A07 | | | D40598J | 5 | | | ALL |
| 2021B | 22 | | GB | CW | 2-5 | 21-31-21 | D02342A | C13 | | | D40182J | 10 | | | 001-099 |
| 2021B | 22 | | GB | CW | 2-0 | 21-31-21 | D02342A | C13 | | | D40182J | 10 | | | 115-199 |
| 2021R | 22 | | GB | CW | 0-0 | 21-31-21 | D02342A | B13 | | | D40182J | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 42

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 2022B | 24 | GL | CX | | 2-5 | 21-31-21 | D02342A | A10 | | | D40182J | 29 | | | 001-099 |
| 2022B | 24 | GL | CX | | 2-0 | 21-31-21 | D02342A | A10 | | | D40182J | 29 | | | 115-199 |
| 2022R | 24 | GL | CX | | 0-0 | 21-31-21 | D02342A | A11 | | | D40182J | 28 | | | ALL |
| 2501B | 22 | GU | BV | | 2-7 | 32-42-12 | D02744A | C09 | | | D42516J | 8 | | | 001-099 |
| 2501R | 22 | GU | BV | | 0-0 | 32-42-12 | D02744A | D09 | | | D42516J | 9 | | | 001-099 |
| 2501Z | | | BV | | 0-0 | 32-42-12 | D02744A | DED | | | D42516J | | | DB | 001-099 |
| 2503B | 24 | G2 | CV | | 2-5 | 21-31-21 | D02342A | C11 | | | D40182J | 7 | | | 001-099 |
| 2503B | 24 | G2 | CV | | 2-0 | 21-31-21 | D02342A | C11 | | | D40182J | 7 | | | 115-199 |
| 2503R | 24 | G2 | CV | | 0-0 | 21-31-21 | D02342A | B11 | | | D40182J | 6 | | | ALL |
| 2503Z | | | CV | | 0-0 | 21-31-21 | D02342A | | | FM | D40182J | 8 | | | ALL |
| 2512B | 22 | GU | BN | | 3-1 | 32-42-11 | D02744B | B06 | | | D42510J | 1 | | | 001-099 |
| 2512R | 22 | GU | BN | | 0-0 | 32-42-11 | D02744B | B05 | | | D42510J | 2 | | | 001-099 |
| 2512Z | | | BN | | 0-0 | 32-42-11 | D02744B | DED | | | D42510J | | | AJ | 001-099 |
| 2513B | 24 | G2 | CH | | 2-3 | 24-11-21 | D02070A | B04 | | | D40398J | 9 | | | 001-099 |
| 2513B | 24 | G2 | CH | | 2-0 | 24-11-21 | D02070A | B04 | | | D40398J | 9 | | | 115-199 |
| 2513R | 24 | G2 | CH | | 0-0 | 24-11-21 | D02070A | A04 | | | D40398J | 2 | | | ALL |
| 2513Z | | | CH | | 0-0 | 24-11-21 | D02070A | C11 | | | D40398J | 17 | | | ALL |
| 2514B | 22 | GU | CI | | 2-4 | 24-21-21 | D02070B | B01 | | | D40398J | 6 | | | 001-099 |
| 2514B | 22 | GU | CI | | 2-0 | 24-21-21 | D02070B | B01 | | | D40398J | 6 | | | 115-199 |
| 2514R | 22 | GU | CI | | 0-0 | 24-21-21 | D02070B | A01 | | | D40398J | 12 | | | ALL |
| 2514Z | | | CI | | 0-0 | 24-21-21 | D02070B | C01 | | | D40398J | 23 | | | ALL |
| 2515B | 22 | GU | BO | | 3-1 | 32-42-11 | D02744B | B13 | | | D42510J | 3 | | | 001-099 |
| 2515R | 22 | GU | BO | | 0-0 | 32-42-11 | D02744B | B12 | | | D42510J | 4 | | | 001-099 |
| 2515Z | | | BO | | 0-0 | 32-42-11 | D02744B | DED | | | D42510J | | | AK | 001-099 |
| 2516B | 22 | GU | BP | | 3-1 | 32-42-11 | D02744A | A06 | | | D42520J | 1 | | | 001-099 |
| 2516R | 22 | GU | BP | | 0-0 | 32-42-11 | D02744A | A05 | | | D42520J | 2 | | | 001-099 |
| 2516Z | | | BP | | 0-0 | 32-42-11 | D02744A | DED | | | D42520J | | | AN | 001-099 |
| 2517B | 22 | GU | BQ | | 3-1 | 32-42-11 | D02744A | A13 | | | D42520J | 3 | | | 001-099 |
| 2517R | 22 | GU | BQ | | 0-0 | 32-42-11 | D02744A | A12 | | | D42520J | 4 | | | 001-099 |
| 2517Z | | | BQ | | 0-0 | 32-42-11 | D02744A | DED | | | D42520J | | | AL | 001-099 |
| 2518B | 22 | GU | BR | | 2-5 | 32-42-11 | D02744B | A06 | | | D42518J | 1 | | | 001-099 |
| 2518R | 22 | GU | BR | | 0-0 | 32-42-11 | D02744B | A05 | | | D42518J | 2 | | | 001-099 |
| 2518Z | | | BR | | 0-0 | 32-42-11 | D02744B | DED | | | D42518J | | | AP | 001-099 |
| 2519B | 22 | GU | BS | | 2-5 | 32-42-11 | D02744B | A13 | | | D42518J | 3 | | | 001-099 |
| 2519R | 22 | GU | BS | | 0-0 | 32-42-11 | D02744B | A12 | | | D42518J | 4 | | | 001-099 |
| 2519Z | | | BS | | 0-0 | 32-42-11 | D02744B | DED | | | D42518J | | | AM | 001-099 |
| 2520B | 22 | GU | BT | | 2-7 | 32-42-11 | D02744A | B06 | | | D42516J | 1 | | | 001-099 |
| 2520R | 22 | GU | BT | | 0-0 | 32-42-11 | D02744A | B05 | | | D42516J | 2 | | | 001-099 |
| 2520Z | | | BT | | 0-0 | 32-42-11 | D02744A | DED | | | D42516J | | | AQ | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 43

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W1284 | 286N1284 | | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 2521B | 22 | GU | BU | | 2-7 | 32-42-11 | D02744A | B13 | | | D42516J | 3 | | | 001-099 | |
| 2521R | 22 | GU | BU | | 0-0 | 32-42-11 | D02744A | B12 | | | D42516J | 4 | | | 001-099 | |
| 2521Z | | | BU | | 0-0 | 32-42-11 | D02744A | DED | | | D42516J | | AR | | 001-099 | |
| 2529B | 22 | GU | BH | | 3-0 | 34-43-14 | TB0184Z | 2 | BJ | | D41379J | 25 | | | 002 | |
| 2529R | 22 | GU | BH | | 0-0 | 34-43-14 | TB0184Z | 1 | BJ | | D41379J | 24 | | | 002 | |
| 2529Z | | | BH | | 0-0 | 34-43-14 | GD02071 | ST.. | 2 | | D41379J | 26 | | | 002 | |
| 3001B | 18 | GC | AX | | 2-6 | 24-21-21 | D02070C | 3 | | | D40398J | 18 | | | 001-099 | |
| 3001B | 18 | GC | AX | | 1-0 | 24-21-21 | D02070C | 3 | | | D40398J | 18 | | | 115-199 | |
| 3001R | 18 | GC | AX | | 0-0 | 24-21-21 | D02070C | 2 | | | D40398J | 20 | | | ALL | |
| 3001Y | 18 | GC | AX | | 0-0 | 24-21-21 | D02070C | 4 | | | D40398J | 22 | | | ALL | |
| 4001B | 24 | GN | CE | | 2-10 | 27-51-11 | D03260A | A07 | | | D41694J | 27 | | | 001-099 | |
| 4001B | 24 | GN | CE | | 3-0 | 27-51-11 | D03260A | A07 | | | D41694J | 27 | | | 115-199 | |
| 4001G | 24 | GN | CE | | 0-0 | 27-51-11 | D03260A | B07 | | | D41694J | 12 | | | ALL | |
| 4001R | 24 | GN | CE | | 0-0 | 27-51-11 | D03260A | A06 | | | D41694J | 13 | | | ALL | |
| 4001Y | 24 | GN | CE | | 0-0 | 27-51-11 | D03260A | B06 | | | D41694J | 28 | | | ALL | |
| 4002B | 24 | GN | CF | | 2-10 | 27-81-11 | D03260A | E07 | | | D41694J | 24 | | | 001-099 | |
| 4002B | 24 | GN | CF | | 3-0 | 27-81-11 | D03260A | E07 | | | D41694J | 24 | | | 115-199 | |
| 4002G | 24 | GN | CF | | 0-0 | 27-81-11 | D03260A | F07 | | | D41694J | 10 | | | ALL | |
| 4002R | 24 | GN | CF | | 0-0 | 27-81-11 | D03260A | E06 | | | D41694J | 11 | | | ALL | |
| 4002Y | 24 | GN | CF | | 0-0 | 27-81-11 | D03260A | F06 | | | D41694J | 25 | | | ALL | |
| 4003B | 22 | GD | CJ | | 2-4 | 24-21-21 | D02070B | B13 | | | D40398J | 1 | | | 001-099 | |
| 4003B | 22 | GD | CJ | | 2-0 | 24-21-21 | D02070B | B13 | | | D40398J | 1 | | | 115-199 | |
| 4003G | 22 | GD | CJ | | 0-0 | 24-21-21 | D02070B | D13 | | | D40398J | 3 | | | ALL | |
| 4003R | 22 | GD | CJ | | 0-0 | 24-21-21 | D02070B | A13 | | | D40398J | 4 | | | ALL | |
| 4003Y | 22 | GD | CJ | | 0-0 | 24-21-21 | D02070B | C13 | | | D40398J | 5 | | | ALL | |
| 4004B | 24 | GN | CL | | 2-7 | 24-23-11 | D02070B | C11 | | | D40894J | 3 | | | 001-099 | |
| 4004B | 24 | GN | CL | | 3-0 | 24-23-11 | D02070B | C11 | | | D40894J | 3 | | | 115-199 | |
| 4004G | 24 | GN | CL | | 0-0 | 24-23-11 | D02070B | D11 | | | D40894J | 4 | | | ALL | |
| 4004R | 24 | GN | CL | | 0-0 | 24-23-11 | D02070B | A11 | | | D40894J | 1 | | | ALL | |
| 4004Y | 24 | GN | CL | | 0-0 | 24-23-11 | D02070B | B11 | | | D40894J | 2 | | | ALL | |
| 4005B | 24 | GN | CM | | 2-8 | 24-23-11 | D02070B | C12 | | | D40492J | 11 | | | 001-099 | |
| 4005B | 24 | GN | CM | | 3-0 | 24-23-11 | D02070B | C12 | | | D40492J | 11 | | | 115-199 | |
| 4005G | 24 | GN | CM | | 0-0 | 24-23-11 | D02070B | D12 | | | D40492J | 10 | | | ALL | |
| 4005R | 24 | GN | CM | | 0-0 | 24-23-11 | D02070B | A12 | | | D40492J | 13 | | | ALL | |
| 4005Y | 24 | GN | CM | | 0-0 | 24-23-11 | D02070B | B12 | | | D40492J | 12 | | | ALL | |
| 4006B | 24 | GN | CN | | 2-8 | 24-23-11 | D02070B | C10 | | | D40492J | 16 | | | 001-099 | |
| 4006B | 24 | GN | CN | | 3-0 | 24-23-11 | D02070B | C10 | | | D40492J | 16 | | | 115-199 | |
| 4006G | 24 | GN | CN | | 0-0 | 24-23-11 | D02070B | D10 | | | D40492J | 14 | | | ALL | |
| 4006R | 24 | GN | CN | | 0-0 | 24-23-11 | D02070B | A10 | | | D40492J | 18 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 44

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 4006Y | 24 | GN | CN | | 0-0 | 24-23-11 | D02070B | B10 | | | D40492J | 17 | | | ALL |
| 4251B | 22 | GW | CP | | 3-3 | 21-31-21 | D02342A | B01 | | | D41694J | 14 | | | 001-099 |
| 4251B | 22 | GW | CP | | 3-0 | 21-31-21 | D02342A | B01 | | | D41694J | 14 | | | 115-199 |
| 4251G | 22 | GW | CP | | 0-0 | 21-31-21 | D02342A | D01 | | | D41694J | 15 | | | ALL |
| 4251R | 22 | GW | CP | | 0-0 | 21-31-21 | D02342A | A01 | | | D41694J | 31 | | | ALL |
| 4251Y | 22 | GW | CP | | 0-0 | 21-31-21 | D02342A | C01 | | | D41694J | 30 | | | ALL |
| 4251Z | | | CP | | 0-0 | 21-31-21 | D02342A | | | FN | D41694J | 32 | | | ALL |
| 5001B | 24 | G2 | AA | | 4-5 | 34-22-29 | D00217B | G03 | | | TB0184Z | 2 | BJ | | 001-099 |
| 5001B | 24 | G2 | AA | | 4-0 | 34-33-21 | D00217B | G03 | | | TB0184Z | 2 | BJ | | 115-199 |
| 5001R | 24 | G2 | AA | | 0-0 | 34-22-29 | D00217B | G02 | | | TB0184Z | 1 | BJ | | 001-099 |
| 5001R | 24 | G2 | AA | | 0-0 | 34-33-21 | D00217B | G02 | | | TB0184Z | 1 | BJ | | 115-199 |
| 5001Z | | | AA | | 0-0 | 34-22-29 | D00217B | DED | | | GD02071 | ST.. | 2 | | 001-099 |
| 5001Z | | | AA | | 0-0 | 34-33-21 | D00217B | DED | | | GD02071 | ST.. | 2 | | 115-199 |
| 5002B | 24 | G2 | AD | | 4-6 | 22-12-21 | D00217B | B03 | | | D41379J | 35 | | | 001-099 |
| 5002B | 24 | G2 | AD | | 4-0 | 22-12-21 | D00217B | B03 | | | D41379J | 35 | | | 115-199 |
| 5002R | 24 | G2 | AD | | 0-0 | 22-12-21 | D00217B | B02 | | | D41379J | 34 | | | ALL |
| 5002Z | | | AD | | 0-0 | 22-12-21 | D00217B | DED | | | D41379J | | | AD | 001-099 |
| 5002Z | | | AD | | 0-0 | 22-12-21 | D00217B | DED | | | D41379J | | | FO | 115-199 |
| 5003B | 22 | GU | ZB | | 2-10 | 32-42-11 | TB0184Y | C038 | BJ | | D02744B | D14 | | | 001-099 |
| 5003R | 22 | GU | ZB | | 0-0 | 32-42-11 | TB0184Y | A038 | BJ | | D02744B | D13 | | | 001-099 |
| 5003Z | | | ZB | | 0-0 | 32-42-11 | D02744B | DED | | | GD02075 | ST.. | 2 | | 001-099 |
| 5004B | 24 | G2 | AF | | 2-5 | 31-41-22 | TB0184Z | 2 | BJ | | D41379J | 5 | | | 001-099 |
| 5004B | 24 | G2 | AF | | 4-0 | 31-41-22 | TB0184Z | 2 | BJ | | D41379J | 5 | | | 115-199 |
| 5004R | 24 | G2 | AF | | 0-0 | 31-41-22 | TB0184Z | 1 | BJ | | D41379J | 4 | | | ALL |
| 5004Z | | | AF | | 0-0 | 31-41-22 | GD02071 | ST.. | 2 | | D41379J | 6 | | | ALL |
| 5005B | 24 | G2 | AG | | 2-5 | 34-22-29 | TB0184Z | 2 | BJ | | D41379J | 2 | | | 001-099 |
| 5005B | 24 | G2 | AG | | 4-0 | 34-22-29 | TB0184Z | 2 | BJ | | D41379J | 2 | | | 115-199 |
| 5005R | 24 | G2 | AG | | 0-0 | 34-22-29 | TB0184Z | 1 | BJ | | D41379J | 1 | | | ALL |
| 5005Z | | | AG | | 0-0 | 34-22-29 | GD02071 | ST.. | 2 | | D41379J | 3 | | | ALL |
| 5006B | 22 | GU | ZA | | 2-8 | 32-42-11 | TB0184Y | C037 | BJ | | D02744A | D12 | | | 001-099 |
| 5006R | 22 | GU | ZA | | 0-0 | 32-42-11 | TB0184Y | A037 | BJ | | D02744A | D11 | | | 001-099 |
| 5006Z | | | ZA | | 0-0 | 32-42-11 | D02744A | DED | | | GD02076 | ST.. | 2 | | 001-099 |
| 5020B | 24 | G2 | AY | | 3-11 | 34-45-02 | D41883J | 8 | | | TB0184Z | 2 | BJ | | 001-099 |
| 5020B | 24 | G2 | AY | | 5-0 | 34-45-02 | D41883J | 8 | | | TB0184Z | 2 | BJ | | 115-199 |
| 5020R | 24 | G2 | AY | | 0-0 | 34-45-02 | D41883J | 7 | | | TB0184Z | 1 | BJ | | ALL |
| 5020Z | | | AY | | 0-0 | 34-45-02 | D41883J | 10 | | | GD02071 | ST.. | 2 | | ALL |
| 5021B | 24 | G2 | CY | | 3-2 | 27-58-31 | D03260B | K13 | | | D41379J | 17 | | | 001-099 |
| 5021B | 24 | G2 | CY | | 3-0 | 27-58-31 | D03260B | K13 | | | D41379J | 17 | | | 115-199 |
| 5021R | 24 | G2 | CY | | 0-0 | 27-58-31 | D03260B | J13 | | | D41379J | 18 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 45

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | E5-2 SHELF (continued) | | | | | | | | | | | |
| 5021Z | | | | CY | 0-0 | 27-58-31 | GD02075 | ST.. | 2 | | D41379J | 21 | | | ALL |
| 5022B | 24 | G2 | | CG | 3-0 | 27-58-31 | D03260A | K13 | | | D41379J | 41 | | | ALL |
| 5022R | 24 | G2 | | CG | 0-0 | 27-58-31 | D03260A | J13 | | | D41379J | 42 | | | ALL |
| 5022Z | | | | CG | 0-0 | 27-58-31 | GD02075 | ST.. | 2 | | D41379J | 43 | | | ALL |
| 5023B | 24 | G2 | | CK | 2-6 | 24-22-22 | D02070A | B12 | | | D40492J | 19 | | | 001-099 |
| 5023B | 24 | G2 | | CK | 3-0 | 24-22-22 | D02070A | B12 | | | D40492J | 19 | | | 115-199 |
| 5023R | 24 | G2 | | CK | 0-0 | 24-22-22 | D02070A | A12 | | | D40492J | 20 | | | ALL |
| 5023Z | | | | CK | 0-0 | 24-22-22 | D02070A | B11 | | | D40492J | 9 | | | ALL |
| 5024B | 24 | G2 | | CQ | 2-6 | 21-31-21 | D02342A | A05 | | | D41883J | 21 | | | 001-099 |
| 5024B | 24 | G2 | | CQ | 3-0 | 21-31-21 | D02342A | A05 | | | D41883J | 21 | | | 115-199 |
| 5024R | 24 | G2 | | CQ | 0-0 | 21-31-21 | D02342A | B06 | | | D41883J | 20 | | | ALL |
| 5024Z | | | | CQ | 0-0 | 21-31-21 | D02342A | | | FL | D41883J | 22 | | | ALL |
| 5025B | 24 | G2 | | CR | 2-6 | 21-31-21 | D02342A | C05 | | | D41327J | 2 | | | 001-099 |
| 5025B | 24 | G2 | | CR | 2-0 | 21-31-21 | D02342A | C05 | | | D41327J | 2 | | | 115-199 |
| 5025R | 24 | G2 | | CR | 0-0 | 21-31-21 | D02342A | D06 | | | D41327J | 1 | | | ALL |
| 5025Z | | | | CR | 0-0 | 21-31-21 | D02342A | | | FL | D41327J | 3 | | | ALL |
| 5026B | 24 | G2 | | AK | 4-0 | 31-31-22 | D41883J | 29 | | | TB0184Z | 2 | BJ | | 115-199 |
| 5026R | 24 | G2 | | AK | 0-0 | 31-31-22 | D41883J | 28 | | | TB0184Z | 1 | BJ | | 115-199 |
| 5026Z | | | | AK | 0-0 | 31-31-22 | D41883J | 30 | | | GD02071 | DC.. | 2 | | 115-199 |
| 5043B | 22 | GU | | C | 2-9 | 32-42-11 | D40190J | 4 | | | TB0184Y | C037 | BJ | | 001-099 |
| 5043R | 22 | GU | | C | 0-0 | 32-42-11 | D40190J | 3 | | | TB0184Y | A037 | BJ | | 001-099 |
| 5043Z | | | | C | 0-0 | 32-42-11 | D40190J | 5 | | | GD02076 | ST.. | 2 | | 001-099 |
| 5044B | 24 | G2 | | D | 2-4 | 27-32-11 | D41327J | 14 | | | TB0184Y | C037 | BJ | | 001-099 |
| 5044R | 24 | G2 | | D | 0-0 | 27-32-11 | D41327J | 13 | | | TB0184Y | A037 | BJ | | 001-099 |
| 5044Z | | | | D | 0-0 | 27-32-11 | D41327J | 15 | | | GD02076 | ST.. | 2 | | 001-099 |
| 5045B | 22 | GU | | E | 2-10 | 32-42-11 | D40492J | 30 | | | TB0184Y | C038 | BJ | | 001-099 |
| 5045R | 22 | GU | | E | 0-0 | 32-42-11 | D40492J | 29 | | | TB0184Y | A038 | BJ | | 001-099 |
| 5045Z | | | | E | 0-0 | 32-42-11 | D40492J | 32 | | | GD02075 | ST.. | 2 | | 001-099 |
| 5046B | 24 | G2 | | F | 3-2 | 27-32-21 | D41883J | 42 | | | TB0184Y | C038 | BJ | | 001-099 |
| 5046R | 24 | G2 | | F | 0-0 | 27-32-21 | D41883J | 41 | | | TB0184Y | A038 | BJ | | 001-099 |
| 5046Z | | | | F | 0-0 | 27-32-21 | D41883J | 43 | | | GD02075 | ST.. | 2 | | 001-099 |
| 5047B | 24 | G2 | | AZ | 3-11 | 31-31-43 | D41883J | 47 | | | TB0184Z | 2 | BJ | | 001-099 |
| 5047R | 24 | G2 | | AZ | 0-0 | 31-31-43 | D41883J | 46 | | | TB0184Z | 1 | BJ | | 001-099 |
| 5047Z | | | | AZ | 0-0 | 31-31-43 | D41883J | 48 | | | GD02071 | DC.. | 2 | | 001-099 |
| 5050B | 24 | G2 | | BC | 3-0 | 34-45-02 | D41379J | 46 | | | TB0184Y | C037 | BJ | | 001-099 |
| 5050R | 24 | G2 | | BC | 0-0 | 34-45-02 | D41379J | 45 | | | TB0184Y | A037 | BJ | | 001-099 |
| 5050Z | | | | BC | 0-0 | 34-45-02 | D41379J | 47 | | | GD02071 | ST.. | 2 | | 001-099 |
| 5051B | 22 | GU | | A | 3-0 | 34-46-12 | D41883J | 35 | | | TB0184Z | 2 | BJ | | 002 |
| 5051R | 22 | GU | | A | 0-0 | 34-46-12 | D41883J | 34 | | | TB0184Z | 1 | BJ | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 46

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------|------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1284 | 286N1284 | | | | E5-2 SHELF (continued) | | | | | | | | | | |
| 5051Z | | | | A | 0-0 | 34-46-12 | D41883J | 36 | | | GD02072 | ST.. | 2 | | 002 |
| FRAD | | | | | 0-0 | 22-12-21 | D41379J | | | AD | D41379J | 36 | | | 001-099 |
| FRAJ | | | | | 0-0 | 32-42-11 | D42510J | 5 | | | D42510J | | | AJ | 001-099 |
| FRAK | | | | | 0-0 | 32-42-11 | D42510J | 6 | | | D42510J | | | AK | 001-099 |
| FRAL | | | | | 0-0 | 32-42-11 | D42520J | 6 | | | D42520J | | | AL | 001-099 |
| FRAM | | | | | 0-0 | 32-42-11 | D42518J | 6 | | | D42518J | | | AM | 001-099 |
| FRAN | | | | | 0-0 | 32-42-11 | D42520J | 5 | | | D42520J | | | AN | 001-099 |
| FRAP | | | | | 0-0 | 32-42-11 | D42518J | 5 | | | D42518J | | | AP | 001-099 |
| FRAQ | | | | | 0-0 | 32-42-11 | D42516J | 5 | | | D42516J | | | AQ | 001-099 |
| FRAR | | | | | 0-0 | 32-42-11 | D42516J | 6 | | | D42516J | | | AR | 001-099 |
| FRDB | | | | | 0-0 | 32-42-12 | D42516J | 7 | | | D42516J | | | DB | 001-099 |
| FRFO | | | | | 1-0 | 22-12-21 | D41379J | | | FO | D41379J | 36 | | | 115-199 |
| W1286 | 286N1286 | | | | E5-3 SHELF | | | | | | | | | | |
| 0001 | 22 | | GA | | 2-5 | 76-11-21 | D03258B | H08 | | | D41419J | 19 | | | 001-099 |
| 0001 | 22 | | GA | | 3-0 | 76-11-21 | D03258B | H08 | | | D41419J | 19 | | | 115-199 |
| 0002 | 24 | | GK | | 3-0 | 34-33-31 | D00223B | F05 | | | GD02082 | DC.. | 2 | | 115-199 |
| 0003 | 20 | | GA | | 2-11 | 34-33-31 | D00223C | 3 | | | GD02082 | AC.. | 2 | | 001-099 |
| 0003 | 20 | | GA | | 3-0 | 34-33-31 | D00223C | 3 | | | GD02082 | AC.. | 2 | | 115-199 |
| 0004 | 22 | | GA | | 3-3 | 34-33-31 | D00223C | 8 | | | D41892J | 1 | | | 001-099 |
| 0004 | 22 | | GA | | 4-0 | 34-33-31 | D00223C | 8 | | | D41892J | 1 | | | 115-199 |
| 0005 | 20 | | GA | | 2-11 | 34-33-31 | D00223C | 2 | | | GD02082 | ST.. | 2 | | 001-099 |
| 0005 | 20 | | GA | | 3-0 | 34-33-31 | D00223C | 2 | | | GD02082 | ST.. | 2 | | 115-199 |
| 0006 | 24 | | GK | | 0-7 | 34-33-31 | D00223B | J06 | | | D00223B | J04 | | | 001-099 |
| 0006 | 24 | | GK | | 1-0 | 34-33-31 | D00223B | J06 | | | D00223B | J04 | | | 115-199 |
| 0007 | 24 | | GK | | 0-7 | 34-33-31 | D00223B | F02 | | | D00223B | F03 | | | 001-099 |
| 0007 | 24 | | GK | | 1-0 | 34-33-31 | D00223B | F02 | | | D00223B | F03 | | | 115-199 |
| 0008 | 24 | | GK | | 0-7 | 34-33-31 | D00223B | C05 | | | D00223B | C06 | | | 001-099 |
| 0008 | 24 | | GK | | 1-0 | 34-33-31 | D00223B | C05 | | | D00223B | C06 | | | 115-199 |
| 0009 | 24 | | GK | | 2-10 | 34-33-31 | D00223B | G05 | | | D41419J | 12 | | | 001-099 |
| 0009 | 24 | | GK | | 3-0 | 34-33-31 | D00223B | G05 | | | D41419J | 12 | | | 115-199 |
| 0010 | 24 | | GK | | 2-9 | 33-24-11 | D03258B | D08 | | | D40590J | 1 | | | 001-099 |
| 0010 | 22 | | GA | | 3-0 | 33-24-11 | D03258B | D08 | | | D40590J | 1 | | | 115-199 |
| 0011 | 22 | | GA | | 2-5 | 22-12-31 | D03258B | E13 | | | D41419J | 1 | | | 001-099 |
| 0011 | 22 | | GA | | 3-0 | 22-12-31 | D03258B | E13 | | | D41419J | 1 | | | 115-199 |
| 0012 | 22 | | GA | | 2-5 | 22-12-31 | D03258B | F13 | | | D41419J | 2 | | | 001-099 |
| 0012 | 22 | | GA | | 3-0 | 22-12-31 | D03258B | F13 | | | D41419J | 2 | | | 115-199 |
| 0013 | 22 | | GA | | 2-5 | 22-24-11 | D03258B | A08 | | | D41419J | 3 | | | 001-099 |
| 0013 | 22 | | GA | | 3-0 | 22-24-11 | D03258B | A08 | | | D41419J | 3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 47

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1286 | 286N1286 | | | E5-3 SHELF (continued) | | | | | | | | | | | |
| 0014 | 22 | | GA | | 3-1 | 34-33-31 | D00223B | | F05 | | GD02082 | DC.. | 2 | | 001-099 |
| 0015 | 22 | | GA | | 3-1 | 34-33-31 | D00223B | | F06 | | GD02082 | DC.. | 2 | | 001-099 |
| 0016 | 24 | | GK | | 2-10 | 34-33-31 | D00223B | | F04 | | D41419J | 11 | | | 001-099 |
| 0016 | 24 | | GK | | 3-0 | 34-33-31 | D00223B | | F04 | | D41419J | 11 | | | 115-199 |
| 0017 | 22 | | GA | | 2-3 | 24-22-12 | D00550A | | A03 | | D41744J | 6 | | | 001-099 |
| 0017 | 22 | | GA | | 2-0 | 24-22-12 | D00550A | | A03 | | D41744J | 6 | | | 115-199 |
| 0018 | 24 | | GK | | 2-3 | 24-22-12 | D00550A | | B04 | | D41744J | 7 | | | 001-099 |
| 0018 | 24 | | GK | | 2-0 | 24-22-12 | D00550A | | B04 | | D41744J | 7 | | | 115-199 |
| 0019 | 22 | | GA | | 2-3 | 74-31-21 | D03258B | | C10 | | D41658J | 10 | | | 001-099 |
| 0019 | 22 | | GA | | 2-0 | 74-31-21 | D03258B | | C10 | | D41658J | 10 | | | 115-199 |
| 0020 | 24 | | GK | | 3-0 | 34-33-31 | D00223B | | F06 | | GD02082 | DC.. | 2 | | 115-199 |
| 0023 | 22 | | GA | | 2-10 | 22-12-31 | D00223B | | K06 | | D41419J | 7 | | | 001-099 |
| 0023 | 22 | | GA | | 3-0 | 22-12-31 | D00223B | | K06 | | D41419J | 7 | | | 115-199 |
| 0025 | 24 | | GK | | 2-7 | 27-81-21 | D41381J | | 10 | | D03258B | G05 | | | 001-099 |
| 0025 | 24 | | GK | | 3-0 | 27-81-21 | D41381J | | 10 | | D03258B | G05 | | | 115-199 |
| 0027 | 22 | | GA | | 2-8 | 33-16-51 | D41463J | | 17 | | D00550B | D03 | | | 001-099 |
| 0027 | 22 | | GA | | 3-0 | 33-16-51 | D41463J | | 17 | | D00550B | D03 | | | 115-199 |
| 0029 | 22 | | GA | | 2-8 | 27-81-21 | D41656J | | 23 | | D03258B | D05 | | | 001-099 |
| 0029 | 22 | | GA | | 3-0 | 27-81-21 | D41656J | | 23 | | D03258B | D05 | | | 115-199 |
| 0030 | 22 | | GA | | 2-8 | 27-81-21 | D41656J | | 24 | | D03258B | E05 | | | 001-099 |
| 0030 | 22 | | GA | | 3-0 | 27-81-21 | D41656J | | 24 | | D03258B | E05 | | | 115-199 |
| 0031 | 24 | | GK | | 3-0 | 24-28-21 | D41463J | | 10 | | TB0185Y | C003 | BJ | | ALL |
| 0032 | 24 | | GK | | 2-5 | 24-28-21 | D00550A | | D04 | | TB0185Y | C003 | BJ | | 001-099 |
| 0032 | 24 | | GK | | 2-0 | 24-28-21 | D00550A | | D04 | | TB0185Y | C003 | BJ | | 115-199 |
| 0033 | 24 | | GK | | 2-4 | 24-28-21 | D00550B | | D04 | | TB0185Y | C003 | BJ | | 001-099 |
| 0033 | 24 | | GK | | 2-0 | 24-28-21 | D00550B | | D04 | | TB0185Y | C003 | BJ | | 115-199 |
| 0034 | 24 | | GK | | 0-7 | 27-58-31 | D03258A | | J10 | | D03258A | J08 | | | 001-099 |
| 0034 | 22 | | GA | | 1-0 | 27-58-31 | D03258A | | J10 | | D03258A | J08 | | | 115-199 |
| 0035 | 24 | | GK | | 0-7 | 27-58-31 | D03258A | | A11 | | D03258A | A08 | | | 001-099 |
| 0035 | 22 | | GA | | 1-0 | 27-58-31 | D03258A | | A11 | | D03258A | A08 | | | 115-199 |
| 0036 | 24 | | GK | | 0-7 | 27-58-31 | D03258A | | B11 | | D03258A | B08 | | | 001-099 |
| 0036 | 22 | | GA | | 1-0 | 27-58-31 | D03258A | | B11 | | D03258A | B08 | | | 115-199 |
| 0037 | 22 | | GA | | 2-9 | 27-58-31 | D03258A | | K15 | | GD02082 | ST.. | 2 | | 001-099 |
| 0037 | 22 | | GA | | 3-0 | 27-58-31 | D03258A | | K15 | | GD02082 | ST.. | 2 | | 115-199 |
| 0041 | 24 | | GK | | 3-0 | 24-28-21 | D41463J | | 9 | | TB0185Y | A003 | BJ | | 115-199 |
| 0042 | 24 | | GK | | 3-0 | 24-28-21 | D01850A | | B02 | | TB0185Y | A003 | BJ | | 115-199 |
| 0043 | 24 | | GK | | 3-0 | 24-28-21 | D01850A | | A10 | | TB0185Y | A003 | BJ | | 115-199 |
| 0046 | 22 | | GA | | 2-1 | 24-41-11 | D00550B | | B08 | | GD02084 | DC.. | 2 | | 001-099 |
| 0046 | 22 | | GA | | 2-0 | 24-41-11 | D00550B | | B08 | | GD02084 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 48

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1286 | | 286N1286 | | | | E5-3 SHELF (continued) | | | | | | | | | |
| 0047 | 22 | GA | | | 2-1 | 24-41-11 | D00550B | D08 | | | GD02084 | DC.. | 2 | | 001-099 |
| 0047 | 22 | GA | | | 2-0 | 24-41-11 | D00550B | D08 | | | GD02084 | DC.. | 2 | | 115-199 |
| 0048 | 22 | GA | | | 2-6 | 24-41-11 | D00550C | 3 | | | D41658J | 7 | | | 001-099 |
| 0048 | 22 | GA | | | 3-0 | 24-41-11 | D00550C | 3 | | | D41658J | 7 | | | 115-199 |
| 0049 | 22 | GA | | | 2-5 | 24-41-11 | D00550A | B10 | | | D40590J | 35 | | | 001-099 |
| 0049 | 22 | GA | | | 3-0 | 24-41-11 | D00550A | B10 | | | D40590J | 35 | | | 115-199 |
| 0051 | 22 | GA | | | 2-8 | 24-41-11 | D41896J | 4 | | | D00550B | B01 | | | 001-099 |
| 0051 | 22 | GA | | | 3-0 | 24-41-11 | D41896J | 4 | | | D00550B | B01 | | | 115-199 |
| 0052 | 24 | GK | | | 2-11 | 24-41-11 | D00550B | A07 | | | D41900J | 32 | | | 001-099 |
| 0052 | 24 | GK | | | 4-0 | 24-41-11 | D00550B | A07 | | | D41900J | 32 | | | 115-199 |
| 0053 | 24 | GK | | | 2-11 | 24-41-11 | D00550B | B07 | | | D41900J | 33 | | | 001-099 |
| 0053 | 24 | GK | | | 4-0 | 24-41-11 | D00550B | B07 | | | D41900J | 33 | | | 115-199 |
| 0054 | 24 | GK | | | 2-11 | 24-41-11 | D00550B | C07 | | | D41900J | 34 | | | 001-099 |
| 0054 | 24 | GK | | | 4-0 | 24-41-11 | D00550B | C07 | | | D41900J | 34 | | | 115-199 |
| 0055 | 24 | GK | | | 2-11 | 24-41-11 | D00550B | A02 | | | D41900J | 35 | | | 001-099 |
| 0055 | 24 | GK | | | 4-0 | 24-41-11 | D00550B | A02 | | | D41900J | 35 | | | 115-199 |
| 0056 | 24 | GK | | | 2-11 | 24-41-11 | D00550B | B02 | | | D41900J | 36 | | | 001-099 |
| 0056 | 24 | GK | | | 4-0 | 24-41-11 | D00550B | B02 | | | D41900J | 36 | | | 115-199 |
| 0057 | 24 | GK | | | 3-3 | 24-41-11 | D41900J | 38 | | | D40590J | 7 | | | 001-099 |
| 0057 | 24 | GK | | | 4-0 | 24-41-11 | D41900J | 38 | | | D40590J | 7 | | | 115-199 |
| 0058 | 24 | GK | | | 3-0 | 24-41-11 | D00550A | D03 | | | D41900J | 37 | | | 001-099 |
| 0058 | 24 | GK | | | 4-0 | 24-41-11 | D00550A | D03 | | | D41900J | 37 | | | 115-199 |
| 0059 | 22 | GA | | | 2-11 | 24-41-11 | D00550B | A12 | | | D41900J | 39 | | | 001-099 |
| 0059 | 22 | GA | | | 4-0 | 24-41-11 | D00550B | A12 | | | D41900J | 39 | | | 115-199 |
| 0060 | 24 | GK | | | 3-0 | 24-41-11 | D00550A | A04 | | | D41900J | 31 | | | 001-099 |
| 0060 | 24 | GK | | | 4-0 | 24-41-11 | D00550A | A04 | | | D41900J | 31 | | | 115-199 |
| 0061 | 22 | GA | | | 2-11 | 24-41-12 | D00550B | A03 | | | D41900J | 9 | | | 001-099 |
| 0061 | 22 | GA | | | 4-0 | 24-41-12 | D00550B | A03 | | | D41900J | 9 | | | 115-199 |
| 0062 | 22 | GA | | | 2-9 | 24-51-14 | D00550B | B14 | | | D41966J | 4 | | | 001-099 |
| 0062 | 22 | GA | | | 3-0 | 24-51-14 | D00550B | B14 | | | D41966J | 4 | | | 115-199 |
| 0063 | 22 | GA | | | 2-2 | 24-51-24 | D00550B | C14 | | | D41381J | 20 | | | 001-099 |
| 0063 | 22 | GA | | | 2-0 | 24-51-24 | D00550B | C14 | | | D41381J | 20 | | | 115-199 |
| 0067 | 24 | GK | | | 2-8 | 24-51-31 | D00550A | D10 | | | D41892J | 3 | | | 001-099 |
| 0067 | 24 | GK | | | 3-0 | 24-51-31 | D00550A | D10 | | | D41892J | 3 | | | 115-199 |
| 0068 | 24 | GK | | | 2-3 | 24-51-51 | D40590J | 36 | | | TB0185Y | C001 | BJ | | 001-099 |
| 0068 | 24 | GK | | | 3-0 | 24-51-51 | D40590J | 36 | | | TB0185Y | C001 | BJ | | 115-199 |
| 0069 | 24 | GK | | | 2-4 | 24-51-51 | D00550B | A01 | | | TB0185Y | C001 | BJ | | 001-099 |
| 0069 | 24 | GK | | | 2-0 | 24-51-51 | D00550B | A01 | | | TB0185Y | C001 | BJ | | 115-199 |
| 0070 | 24 | GK | | | 3-3 | 24-51-51 | D41900J | 40 | | | TB0185Y | C001 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 49

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1286 | 286N1286 | | | E5-3 SHELF (continued) | | | | | | | | | | | |
| 0070 | 24 | | GK | | 4-0 | 24-51-51 | D41900J | | 40 | | TB0185Y | C001 | BJ | | 115-199 |
| 0071 | 22 | | GA | | 2-11 | 24-51-51 | D41900J | | 41 | | D00550B | D11 | | | 001-099 |
| 0071 | 22 | | GA | | 4-0 | 24-51-51 | D41900J | | 41 | | D00550B | D11 | | | 115-199 |
| 0072 | 22 | | GA | | 2-11 | 24-51-51 | D41900J | | 42 | | D00550B | C11 | | | 001-099 |
| 0072 | 22 | | GA | | 4-0 | 24-51-51 | D41900J | | 42 | | D00550B | C11 | | | 115-199 |
| 0073 | 24 | | GK | | 3-0 | 24-51-51 | D41900J | | 43 | | D00550A | C10 | | | 001-099 |
| 0073 | 24 | | GK | | 4-0 | 24-51-51 | D41900J | | 43 | | D00550A | C10 | | | 115-199 |
| 0074 | 22 | | GA | | 2-11 | 24-51-61 | D41900J | | 3 | | D00550B | A11 | | | 001-099 |
| 0074 | 22 | | GA | | 4-0 | 24-51-61 | D41900J | | 3 | | D00550B | A11 | | | 115-199 |
| 0075 | 22 | | GA | | 2-11 | 24-51-61 | D41900J | | 2 | | D00550B | B11 | | | 001-099 |
| 0075 | 22 | | GA | | 4-0 | 24-51-61 | D41900J | | 2 | | D00550B | B11 | | | 115-199 |
| 0076 | 22 | | GA | | 2-0 | 33-31-31 | D41900J | | 45 | | D41644J | 3 | | | 115-199 |
| 0077 | 22 | | GA | | 2-2 | 25-31-33 | D00550B | B12 | | | D41744J | 1 | | | 001-099 |
| 0077 | 22 | | GA | | 2-0 | 25-31-33 | D00550B | B12 | | | D41744J | 1 | | | 115-199 |
| 0078 | 22 | | GA | | 3-0 | 25-31-21 | D41750J | | 17 | | D00550B | C12 | | | 115-199 |
| 0080 | 22 | | GA | | 3-0 | 24-21-41 | D41900J | | 1 | | D01850B | A15 | | | 115-199 |
| 0081 | 22 | | GA | | 3-0 | 24-21-41 | D41900J | | 8 | | D01850B | B15 | | | 115-199 |
| 0082 | 22 | | GA | | 3-0 | 24-21-41 | D41900J | | 14 | | D01850B | C15 | | | 115-199 |
| 0084 | 24 | | GK | | 2-5 | 24-51-14 | D00550A | C09 | | | TB0185Y | A006 | BJ | | 001-099 |
| 0084 | 24 | | GK | | 3-0 | 24-51-14 | D00550A | C09 | | | D40590J | 3 | | | 115-199 |
| 0085 | 24 | | GK | | 2-5 | 24-51-24 | D00550A | D09 | | | TB0185Y | A002 | BJ | | 001-099 |
| 0085 | 24 | | GK | | 2-0 | 24-51-24 | D00550A | D09 | | | TB0185Y | A002 | BJ | | 115-199 |
| 0086 | 24 | | GK | | 2-5 | 24-51-24 | D00550A | A10 | | | TB0185Y | A002 | BJ | | 001-099 |
| 0086 | 24 | | GK | | 2-0 | 24-51-24 | D00550A | A10 | | | TB0185Y | A002 | BJ | | 115-199 |
| 0087 | 24 | | GK | | 2-3 | 24-51-24 | D40590J | 2 | | | TB0185Y | A002 | BJ | | 001-099 |
| 0087 | 24 | | GK | | 3-0 | 24-51-24 | D40590J | 2 | | | TB0185Y | A002 | BJ | | 115-199 |
| 0106 | 24 | | GK | | 2-4 | 27-32-11 | D03258B | E10 | | | D41463J | 3 | | | 001-099 |
| 0106 | 24 | | GK | | 3-0 | 27-32-11 | D03258B | E10 | | | D41463J | 3 | | | 115-199 |
| 0107 | 24 | | GK | | 2-4 | 27-32-11 | D03258B | A10 | | | D41463J | 4 | | | 001-099 |
| 0107 | 24 | | GK | | 3-0 | 27-32-11 | D03258B | A10 | | | D41463J | 4 | | | 115-199 |
| 0110 | 24 | | GK | | 2-5 | 27-32-11 | D03258A | F09 | | | D41463J | 7 | | | 001-099 |
| 0110 | 24 | | GK | | 3-0 | 27-32-11 | D03258A | F09 | | | D41463J | 7 | | | 115-199 |
| 0115 | 24 | | GK | | 2-4 | 27-32-11 | D03258B | H10 | | | D41463J | 8 | | | 001-099 |
| 0115 | 24 | | GK | | 3-0 | 27-32-11 | D03258B | H10 | | | D41463J | 8 | | | 115-199 |
| 0116 | 24 | | GK | | 3-0 | 27-32-11 | D41463J | 11 | | | D40590J | 5 | | | 001-099 |
| 0116 | 24 | | GK | | 4-0 | 27-32-11 | D41463J | 11 | | | D40590J | 5 | | | 115-199 |
| 0133 | 24 | | GK | | 2-3 | 24-22-22 | D00550A | C03 | | | D41744J | 10 | | | 001-099 |
| 0133 | 24 | | GK | | 2-0 | 24-22-22 | D00550A | C03 | | | D41744J | 10 | | | 115-199 |
| 0134 | 24 | | GK | | 2-6 | 24-22-22 | D00550A | B03 | | | D41750J | 14 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 50

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1286 | | 286N1286 | | | | E5-3 SHELF (continued) | | | | | | | | | |
| 0134 | 24 | GK | | | 3-0 | 24-22-22 | D00550A | B03 | | | D41750J | 14 | | | 115-199 |
| 0135 | 24 | GK | | | 2-6 | 24-22-22 | D00550A | C04 | | | D41750J | 13 | | | 001-099 |
| 0135 | 24 | GK | | | 3-0 | 24-22-22 | D00550A | C04 | | | D41750J | 13 | | | 115-199 |
| 0138 | 22 | GA | | | 3-0 | 24-22-41 | D41896J | 7 | | | D01850B | A03 | | | 115-199 |
| 0139 | 22 | GA | | | 4-0 | 24-22-41 | D41868J | 1 | | | D01850B | D02 | | | 115-199 |
| 0140 | 24 | GK | | | 4-0 | 24-22-41 | D41868J | 2 | | | D01850A | B05 | | | 115-199 |
| 0141 | 24 | GK | | | 4-0 | 24-22-41 | D41868J | 4 | | | D01850A | A05 | | | 115-199 |
| 0142 | 24 | GK | | | 4-0 | 24-22-41 | D41868J | 3 | | | D01850A | D04 | | | 115-199 |
| 0143 | 22 | GA | | | 3-0 | 24-22-41 | D41644J | 1 | | | D01850A | A06 | | | 115-199 |
| 0144 | 22 | GA | | | 3-0 | 24-22-22 | D41381J | 19 | | | D01850A | A01 | | | 115-199 |
| 0145 | 24 | GK | | | 4-0 | 24-22-41 | D41868J | 5 | | | D01850A | C02 | | | 115-199 |
| 0146 | 22 | GA | | | 3-0 | 24-22-41 | D41900J | 10 | | | D01850A | C05 | | | 115-199 |
| 0147 | 22 | GA | | | 3-0 | 24-22-41 | D41900J | 5 | | | D01850A | B01 | | | 115-199 |
| 0148 | 22 | GA | | | 3-0 | 24-22-41 | D41900J | 6 | | | D01850A | C01 | | | 115-199 |
| 0149 | 24 | GK | | | 3-0 | 24-22-41 | D41900J | 7 | | | D01850A | D06 | | | 115-199 |
| 0150 | 22 | GA | | | 3-0 | 24-22-41 | D41900J | 12 | | | D01850A | C15 | | | 115-199 |
| 0151 | 24 | GK | | | 3-5 | 24-27-41 | D41868J | 7 | | | D41900J | 44 | | | 001-099 |
| 0151 | 24 | GK | | | 5-0 | 24-27-41 | D41868J | 7 | | | D41900J | 44 | | | 115-199 |
| 0152 | 24 | GK | | | 3-5 | 24-27-41 | D41868J | 8 | | | D41900J | 13 | | | 001-099 |
| 0152 | 24 | GK | | | 5-0 | 24-27-41 | D41868J | 8 | | | D41900J | 13 | | | 115-199 |
| 0153 | 22 | GA | | | 2-11 | 27-23-21 | D41381J | 2 | | | D41828J | 9 | | | 001-099 |
| 0153 | 22 | GA | | | 4-0 | 27-23-21 | D41381J | 2 | | | D41828J | 9 | | | 115-199 |
| 0154 | 22 | GA | | | 2-11 | 27-23-21 | D41381J | 3 | | | D41828J | 8 | | | 001-099 |
| 0154 | 22 | GA | | | 4-0 | 27-23-21 | D41381J | 3 | | | D41828J | 8 | | | 115-199 |
| 0155 | 24 | GK | | | 3-0 | 24-41-11 | D01850A | D07 | | | D41900J | 11 | | | 115-199 |
| 0159 | 24 | GK | | | 5-0 | 24-22-41 | D41900J | 19 | | | D41868J | 6 | | | 115-199 |
| 0187 | 24 | GK | | | 2-5 | 27-51-61 | D42053J | 9 | | | D03258A | A09 | | | 001-099 |
| 0187 | 24 | GK | | | 3-0 | 27-51-61 | D42053J | 9 | | | D03258A | A09 | | | 115-199 |
| 0188 | 24 | GK | | | 2-5 | 27-51-61 | D42053J | 10 | | | D03258A | B09 | | | 001-099 |
| 0188 | 24 | GK | | | 3-0 | 27-51-61 | D42053J | 10 | | | D03258A | B09 | | | 115-199 |
| 0189 | 22 | GA | | | 2-10 | 27-51-61 | D03258A | D04 | | | GD02083 | AC.. | 2 | | 001-099 |
| 0189 | 22 | GA | | | 3-0 | 27-51-61 | D03258A | D04 | | | GD02083 | AC.. | 2 | | 115-199 |
| 0190 | 24 | GK | | | 2-6 | 27-51-61 | D41966J | 2 | | | D03258A | H03 | | | 001-099 |
| 0190 | 24 | GK | | | 3-0 | 27-51-61 | D41966J | 2 | | | D03258A | H03 | | | 115-199 |
| 0191 | 24 | GK | | | 2-6 | 27-51-61 | D41966J | 1 | | | D03258A | D03 | | | 001-099 |
| 0191 | 24 | GK | | | 3-0 | 27-51-61 | D41966J | 1 | | | D03258A | D03 | | | 115-199 |
| 0192 | 24 | GK | | | 2-6 | 27-51-61 | D41966J | 3 | | | D03258A | F03 | | | 001-099 |
| 0192 | 24 | GK | | | 3-0 | 27-51-61 | D41966J | 3 | | | D03258A | F03 | | | 115-199 |
| 0193 | 12 | GA | | | 2-6 | 27-51-61 | GD03037 | DC.. | E | | D03258C | 8 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 51

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1286 | 286N1286 | | | E5-3 SHELF (continued) | | | | | | | | | | | |
| 0193 | 12 | | GA | | 3-0 | 27-51-61 | GD03037 | DC.. | E | | D03258C | 8 | | | 115-199 |
| 0194 | 22 | | GA | | 2-10 | 27-51-61 | GD02083 | AC.. | 2 | | D03258A | F04 | | | 001-099 |
| 0194 | 22 | | GA | | 3-0 | 27-51-61 | GD02083 | AC.. | 2 | | D03258A | F04 | | | 115-199 |
| 0195 | 24 | | GK | | 2-5 | 27-51-61 | D42053J | | 11 | | D03258A | B10 | | | 001-099 |
| 0195 | 24 | | GK | | 3-0 | 27-51-61 | D42053J | | 11 | | D03258A | B10 | | | 115-199 |
| 0196 | 24 | | GK | | 2-5 | 27-51-61 | D42053J | | 12 | | D03258A | C10 | | | 001-099 |
| 0196 | 24 | | GK | | 3-0 | 27-51-61 | D42053J | | 12 | | D03258A | C10 | | | 115-199 |
| 0197 | 24 | | GK | | 2-5 | 27-51-61 | D42053J | | 13 | | D03258A | D10 | | | 001-099 |
| 0197 | 24 | | GK | | 3-0 | 27-51-61 | D42053J | | 13 | | D03258A | D10 | | | 115-199 |
| 0198 | 24 | | GK | | 2-5 | 27-51-61 | D42053J | | 14 | | D03258A | E10 | | | 001-099 |
| 0198 | 24 | | GK | | 3-0 | 27-51-61 | D42053J | | 14 | | D03258A | E10 | | | 115-199 |
| 0199 | 24 | | GK | | 2-5 | 27-51-61 | D42053J | | 15 | | D03258A | F10 | | | 001-099 |
| 0199 | 24 | | GK | | 3-0 | 27-51-61 | D42053J | | 15 | | D03258A | F10 | | | 115-199 |
| 0200 | 24 | | GK | | 2-5 | 27-51-61 | D42053J | | 6 | | D03258A | G10 | | | 001-099 |
| 0200 | 24 | | GK | | 3-0 | 27-51-61 | D42053J | | 6 | | D03258A | G10 | | | 115-199 |
| 0201 | 24 | | GK | | 2-5 | 27-51-61 | D42053J | | 7 | | D03258A | K09 | | | 001-099 |
| 0201 | 24 | | GK | | 3-0 | 27-51-61 | D42053J | | 7 | | D03258A | K09 | | | 115-199 |
| 0202 | 24 | | GK | | 2-5 | 27-51-61 | D42053J | | 8 | | D03258A | A10 | | | 001-099 |
| 0202 | 24 | | GK | | 3-0 | 27-51-61 | D42053J | | 8 | | D03258A | A10 | | | 115-199 |
| 0205 | 24 | | GK | | 2-4 | 27-58-11 | D41329J | | 11 | | D03258B | H05 | | | 001-099 |
| 0205 | 24 | | GK | | 3-0 | 27-58-11 | D41329J | | 11 | | D03258B | H05 | | | 115-199 |
| 0211 | 22 | | GA | | 3-0 | 24-22-41 | D01850B | A08 | | | GD02088 | ST.. | 2 | | 115-199 |
| 0245 | 24 | | GK | | 2-4 | 27-51-61 | D41329J | | 8 | | D03258B | A06 | | | 001-099 |
| 0245 | 24 | | GK | | 3-0 | 27-51-61 | D41329J | | 8 | | D03258B | A06 | | | 115-199 |
| 0246 | 24 | | GK | | 2-4 | 27-51-61 | D41329J | | 7 | | D03258B | B06 | | | 001-099 |
| 0246 | 24 | | GK | | 3-0 | 27-51-61 | D41329J | | 7 | | D03258B | B06 | | | 115-199 |
| 0247 | 24 | | GK | | 2-4 | 27-51-61 | D41329J | | 10 | | D03258B | J05 | | | 001-099 |
| 0247 | 24 | | GK | | 3-0 | 27-51-61 | D41329J | | 10 | | D03258B | J05 | | | 115-199 |
| 0248 | 24 | | GK | | 2-4 | 27-51-61 | D41329J | | 9 | | D03258B | K05 | | | 001-099 |
| 0248 | 24 | | GK | | 3-0 | 27-51-61 | D41329J | | 9 | | D03258B | K05 | | | 115-199 |
| 0249 | 24 | | GK | | 2-3 | 27-51-61 | D41658J | | 8 | | D03258B | D06 | | | 001-099 |
| 0249 | 24 | | GK | | 3-0 | 27-51-61 | D41658J | | 8 | | D03258B | D06 | | | 115-199 |
| 0250 | 24 | | GK | | 2-4 | 27-51-61 | D41329J | | 6 | | D03258B | C06 | | | 001-099 |
| 0250 | 24 | | GK | | 3-0 | 27-51-61 | D41329J | | 6 | | D03258B | C06 | | | 115-199 |
| 0251 | 24 | | GK | | 2-5 | 27-58-31 | TB0185Y | C002 | BJ | | D41419J | 14 | | | 001-099 |
| 0251 | 24 | | GK | | 3-0 | 27-58-31 | TB0185Y | C002 | BJ | | D41419J | 14 | | | 115-199 |
| 0252 | 24 | | GK | | 2-9 | 27-58-31 | D03258B | E11 | | | TB0185Y | A001 | BJ | | 001-099 |
| 0252 | 24 | | GK | | 3-0 | 27-58-31 | D03258B | E11 | | | TB0185Y | A001 | BJ | | 115-199 |
| 0253 | 24 | | GK | | 2-6 | 27-58-31 | D41381J | | 5 | | TB0185Y | A001 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 52

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1286 | 286N1286 | | | E5-3 SHELF (continued) | | | | | | | | | | | | |
| 0253 | 24 | | GK | | 3-0 | 27-58-31 | D41381J | | 5 | | | TB0185Y | A001 | BJ | | 115-199 |
| 0254 | 24 | | GK | | 3-0 | 27-58-31 | D41329J | | 15 | | | TB0185Y | A001 | BJ | | ALL |
| 0255 | 24 | | GK | | 2-5 | 27-58-31 | D41419J | | 13 | | | TB0185Y | A001 | BJ | | 001-099 |
| 0255 | 24 | | GK | | 3-0 | 27-58-31 | D41419J | | 13 | | | TB0185Y | A001 | BJ | | 115-199 |
| 0257 | 22 | | GA | | 2-6 | 27-81-31 | D41381J | | 18 | | | TB0185Y | A004 | BJ | | 001-099 |
| 0257 | 22 | | GA | | 3-0 | 27-81-31 | D41381J | | 18 | | | TB0185Y | A004 | BJ | | 115-199 |
| 0258 | 22 | | GA | | 3-1 | 27-81-31 | D41828J | | 7 | | | TB0185Y | A004 | BJ | | 001-099 |
| 0258 | 22 | | GA | | 4-0 | 27-81-31 | D41828J | | 7 | | | TB0185Y | A004 | BJ | | 115-199 |
| 0259 | 22 | | GA | | 2-10 | 27-81-31 | D03258A | G09 | | | | TB0185Y | A004 | BJ | | 001-099 |
| 0259 | 22 | | GA | | 3-0 | 27-81-31 | D03258A | G09 | | | | TB0185Y | A004 | BJ | | 115-199 |
| 0260 | 22 | | GA | | 2-4 | 74-31-11 | D41463J | | 13 | | | D03258B | D10 | | | 001-099 |
| 0260 | 22 | | GA | | 3-0 | 74-31-11 | D41329J | | 20 | | | D03258B | D10 | | | 115-199 |
| 0261 | 22 | | GA | | 2-8 | 27-48-21 | D41892J | | 9 | | | D41419J | 20 | | | 001-099 |
| 0261 | 22 | | GA | | 3-0 | 27-48-21 | D41892J | | 9 | | | D41419J | 20 | | | 115-199 |
| 0262 | 24 | | GK | | 2-9 | 27-58-31 | D03258B | D11 | | | | TB0185Y | C002 | BJ | | 001-099 |
| 0262 | 24 | | GK | | 3-0 | 27-58-31 | D03258B | D11 | | | | TB0185Y | C002 | BJ | | 115-199 |
| 0263 | 24 | | GK | | 2-6 | 27-58-31 | D41381J | | 16 | | | TB0185Y | C002 | BJ | | 001-099 |
| 0263 | 24 | | GK | | 3-0 | 27-58-31 | D41381J | | 16 | | | TB0185Y | C002 | BJ | | 115-199 |
| 0266 | 22 | | GA | | 3-0 | 24-22-41 | D01850B | D15 | | | | GD02088 | DC.. | 2 | | 115-199 |
| 0267 | 24 | | GK | | 2-4 | 31-51-41 | D03258B | E08 | | | | D41463J | 44 | | | 001-099 |
| 0267 | 24 | | GK | | 3-0 | 31-51-41 | D03258B | E08 | | | | D41463J | 44 | | | 115-199 |
| 0268 | 24 | | GK | | 2-4 | 31-51-41 | D03258B | G10 | | | | D41463J | 45 | | | 001-099 |
| 0268 | 24 | | GK | | 3-0 | 31-51-41 | D03258B | G10 | | | | D41463J | 45 | | | 115-199 |
| 0270 | 24 | | GK | | 2-4 | 24-51-71 | D40590J | 6 | | | | D00550B | A10 | | | 001-099 |
| 0270 | 24 | | GK | | 3-0 | 24-51-71 | D40590J | 6 | | | | D00550B | A10 | | | 115-199 |
| 0275 | 24 | | GK | | 2-5 | 24-51-14 | D00550A | A09 | | | | TB0185Y | A006 | BJ | | 001-099 |
| 0276 | 24 | | GK | | 2-3 | 24-51-14 | D40590J | 3 | | | | TB0185Y | A006 | BJ | | 001-099 |
| 0305 | 22 | | GA | | 2-4 | 25-31-11 | D41750J | 18 | | | | D00550B | C12 | | | 001-099 |
| 0402 | 22 | | GA | | 3-0 | 24-22-41 | D01850A | A11 | | | | GD02088 | DC.. | 2 | | 115-199 |
| 2006B | 24 | | GL | AW | 2-4 | 27-32-11 | D03258B | D13 | | | | D41463J | 2 | | | 001-099 |
| 2006B | 24 | | GL | AW | 3-0 | 27-32-11 | D03258B | D13 | | | | D41463J | 2 | | | 115-199 |
| 2006R | 24 | | GL | AW | 0-0 | 27-32-11 | D03258B | C13 | | | | D41463J | 1 | | | ALL |
| 2022B | 24 | | GL | CH | 2-8 | 27-51-61 | D41656J | 5 | | | | D03258B | B03 | | | 001-099 |
| 2022B | 24 | | GL | CH | 3-0 | 27-51-61 | D41656J | 5 | | | | D03258B | B03 | | | 115-199 |
| 2022R | 24 | | GL | CH | 0-0 | 27-51-61 | D41656J | 6 | | | | D03258B | A03 | | | ALL |
| 2023B | 24 | | GL | CK | 2-8 | 27-51-61 | D41656J | 3 | | | | D03258B | F03 | | | 001-099 |
| 2023B | 24 | | GL | CK | 3-0 | 27-51-61 | D41656J | 3 | | | | D03258B | F03 | | | 115-199 |
| 2023R | 24 | | GL | CK | 0-0 | 27-51-61 | D41656J | 4 | | | | D03258B | E03 | | | ALL |
| 2024B | 24 | | GL | CM | 2-5 | 27-51-61 | D41828J | 6 | | | | D03258B | H03 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 53

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1286 | 286N1286 | | | E5-3 SHELF (continued) | | | | | | | | | | | |
| 2024B | 24 | GL | CM | | 3-0 | 27-51-61 | D41828J | | 6 | | D03258B | H03 | | | 115-199 |
| 2024R | 24 | GL | CM | | 0-0 | 27-51-61 | D41828J | | 5 | | D03258B | G03 | | | ALL |
| 2025B | 24 | GL | CP | | 2-3 | 27-51-61 | D41658J | | 1 | | D03258B | D03 | | | 001-099 |
| 2025B | 24 | GL | CP | | 2-0 | 27-51-61 | D41658J | | 1 | | D03258B | D03 | | | 115-199 |
| 2025R | 24 | GL | CP | | 0-0 | 27-51-61 | D41658J | | 2 | | D03258B | C03 | | | ALL |
| 2506B | 22 | GU | BD | | 2-0 | 24-21-41 | D41644J | | 9 | | D01850B | B01 | | | 115-199 |
| 2506R | 22 | GU | BD | | 0-0 | 24-21-41 | D41644J | | 8 | | D01850B | A01 | | | 115-199 |
| 2506Z | | | BD | | 0-0 | 24-21-41 | D41644J | | 14 | | D01850B | C01 | | | 115-199 |
| 3003B | 20 | GC | BB | | 2-0 | 24-21-41 | D41644J | | 6 | | D01850C | 3 | | | 115-199 |
| 3003R | 20 | GC | BB | | 0-0 | 24-21-41 | D41644J | | 5 | | D01850C | 2 | | | 115-199 |
| 3003Y | 20 | GC | BB | | 0-0 | 24-21-41 | D41644J | | 7 | | D01850C | 4 | | | 115-199 |
| 4001B | 24 | GN | BA | | 3-0 | 24-23-12 | D41900J | | 23 | | D00550A | C02 | | | 001-099 |
| 4001B | 24 | GN | BA | | 4-0 | 24-23-12 | D41900J | | 23 | | D00550A | C02 | | | 115-199 |
| 4001G | 24 | GN | BA | | 0-0 | 24-23-12 | D41900J | | 24 | | D00550A | D02 | | | ALL |
| 4001R | 24 | GN | BA | | 0-0 | 24-23-12 | D41900J | | 25 | | D00550A | A02 | | | ALL |
| 4001Y | 24 | GN | BA | | 0-0 | 24-23-12 | D41900J | | 26 | | D00550A | B02 | | | ALL |
| 4002B | 24 | GN | BC | | 2-0 | 24-21-41 | D41644J | | 10 | | D01850B | B13 | | | 115-199 |
| 4002G | 24 | GN | BC | | 0-0 | 24-21-41 | D41644J | | 11 | | D01850B | D13 | | | 115-199 |
| 4002R | 24 | GN | BC | | 0-0 | 24-21-41 | D41644J | | 12 | | D01850B | A13 | | | 115-199 |
| 4002Y | 24 | GN | BC | | 0-0 | 24-21-41 | D41644J | | 13 | | D01850B | C13 | | | 115-199 |
| 4003B | 24 | GN | CU | | 2-3 | 24-23-12 | D41744J | | 2 | | D00550A | C05 | | | 001-099 |
| 4003B | 24 | GN | CU | | 2-0 | 24-23-12 | D41744J | | 2 | | D00550A | C05 | | | 115-199 |
| 4003G | 24 | GN | CU | | 0-0 | 24-23-12 | D41744J | | 3 | | D00550A | D05 | | | ALL |
| 4003R | 24 | GN | CU | | 0-0 | 24-23-12 | D41744J | | 4 | | D00550A | A05 | | | ALL |
| 4003Y | 24 | GN | CU | | 0-0 | 24-23-12 | D41744J | | 5 | | D00550A | B05 | | | ALL |
| 4004B | 24 | GN | CV | | 3-0 | 24-23-11 | D41900J | | 15 | | D01850B | C12 | | | 115-199 |
| 4004G | 24 | GN | CV | | 0-0 | 24-23-11 | D41900J | | 16 | | D01850B | D12 | | | 115-199 |
| 4004R | 24 | GN | CV | | 0-0 | 24-23-11 | D41900J | | 17 | | D01850B | A12 | | | 115-199 |
| 4004Y | 24 | GN | CV | | 0-0 | 24-23-11 | D41900J | | 18 | | D01850B | B12 | | | 115-199 |
| 4005B | 24 | GN | CW | | 2-6 | 24-23-12 | D41750J | | 6 | | D00550A | C07 | | | 001-099 |
| 4005B | 24 | GN | CW | | 3-0 | 24-23-12 | D41750J | | 6 | | D00550A | C07 | | | 115-199 |
| 4005G | 24 | GN | CW | | 0-0 | 24-23-12 | D41750J | | 7 | | D00550A | D07 | | | ALL |
| 4005R | 24 | GN | CW | | 0-0 | 24-23-12 | D41750J | | 8 | | D00550A | A07 | | | ALL |
| 4005Y | 24 | GN | CW | | 0-0 | 24-23-12 | D41750J | | 9 | | D00550A | B07 | | | ALL |
| 4006B | 24 | GN | CX | | 3-0 | 24-23-12 | D41900J | | 22 | | D00550A | C06 | | | 001-099 |
| 4006B | 24 | GN | CX | | 4-0 | 24-23-12 | D41900J | | 22 | | D00550A | C06 | | | 115-199 |
| 4006G | 24 | GN | CX | | 0-0 | 24-23-12 | D41900J | | 20 | | D00550A | D06 | | | ALL |
| 4006R | 24 | GN | CX | | 0-0 | 24-23-12 | D41900J | | 21 | | D00550A | A06 | | | ALL |
| 4006Y | 24 | GN | CX | | 0-0 | 24-23-12 | D41900J | | 4 | | D00550A | B06 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 54

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1286 | 286N1286 | | | E5-3 SHELF (continued) | | | | | | | | | | | |
| 4007B | 24 | | GN | CY | 2-6 | 27-51-61 | D41828J | | 1 | | | D03258A | G06 | | 001-099 |
| 4007B | 24 | | GN | CY | 3-0 | 27-51-61 | D41828J | | 1 | | | D03258A | G06 | | 115-199 |
| 4007G | 24 | | GN | CY | 0-0 | 27-51-61 | D41828J | | 2 | | | D03258A | H07 | | ALL |
| 4007R | 24 | | GN | CY | 0-0 | 27-51-61 | D41828J | | 3 | | | D03258A | G07 | | ALL |
| 4007Y | 24 | | GN | CY | 0-0 | 27-51-61 | D41828J | | 4 | | | D03258A | H06 | | ALL |
| 4008B | 24 | | GN | CZ | 2-9 | 27-51-61 | D41656J | | 7 | | | D03258A | E07 | | 001-099 |
| 4008B | 24 | | GN | CZ | 3-0 | 27-51-61 | D41656J | | 7 | | | D03258A | E07 | | 115-199 |
| 4008G | 24 | | GN | CZ | 0-0 | 27-51-61 | D41656J | | 8 | | | D03258A | F07 | | ALL |
| 4008R | 24 | | GN | CZ | 0-0 | 27-51-61 | D41656J | | 9 | | | D03258A | E06 | | ALL |
| 4008Y | 24 | | GN | CZ | 0-0 | 27-51-61 | D41656J | | 10 | | | D03258A | F06 | | ALL |
| 4009B | 24 | | GN | DA | 2-9 | 27-51-61 | D41656J | | 11 | | | D03258A | A07 | | 001-099 |
| 4009B | 24 | | GN | DA | 3-0 | 27-51-61 | D41656J | | 11 | | | D03258A | A07 | | 115-199 |
| 4009G | 24 | | GN | DA | 0-0 | 27-51-61 | D41656J | | 12 | | | D03258A | B07 | | ALL |
| 4009R | 24 | | GN | DA | 0-0 | 27-51-61 | D41656J | | 13 | | | D03258A | A06 | | ALL |
| 4009Y | 24 | | GN | DA | 0-0 | 27-51-61 | D41656J | | 14 | | | D03258A | B06 | | ALL |
| 4010B | 24 | | GN | DB | 2-5 | 27-51-61 | D41658J | | 3 | | | D03258A | C07 | | 001-099 |
| 4010B | 24 | | GN | DB | 2-0 | 27-51-61 | D41658J | | 3 | | | D03258A | C07 | | 115-199 |
| 4010G | 24 | | GN | DB | 0-0 | 27-51-61 | D41658J | | 4 | | | D03258A | D07 | | ALL |
| 4010R | 24 | | GN | DB | 0-0 | 27-51-61 | D41658J | | 5 | | | D03258A | C06 | | ALL |
| 4010Y | 24 | | GN | DB | 0-0 | 27-51-61 | D41658J | | 6 | | | D03258A | D06 | | ALL |
| 4011B | 24 | | GN | DH | 3-0 | 24-41-11 | D00550A | | C01 | | | D41900J | 27 | | 001-099 |
| 4011B | 24 | | GN | DH | 4-0 | 24-41-11 | D00550A | | C01 | | | D41900J | 27 | | 115-199 |
| 4011G | 24 | | GN | DH | 0-0 | 24-41-11 | D00550A | | D01 | | | D41900J | 28 | | ALL |
| 4011R | 24 | | GN | DH | 0-0 | 24-41-11 | D00550A | | A01 | | | D41900J | 29 | | ALL |
| 4011Y | 24 | | GN | DH | 0-0 | 24-41-11 | D00550A | | B01 | | | D41900J | 30 | | ALL |
| 5001B | 24 | | G2 | AF | 2-5 | 27-58-31 | D03258A | | K13 | | | D41329J | 13 | | 001-099 |
| 5001B | 24 | | G2 | AF | 3-0 | 27-58-31 | D03258A | | K13 | | | D41329J | 13 | | 115-199 |
| 5001R | 24 | | G2 | AF | 0-0 | 27-58-31 | D03258A | | J13 | | | D41329J | 14 | | ALL |
| 5001Z | | | | AF | 0-0 | 27-58-31 | GD02084 | | ST.. | 2 | | D41329J | 12 | | ALL |
| 5002B | 24 | | G2 | AG | 2-7 | 27-58-31 | D03258B | | K13 | | | D41381J | 6 | | 001-099 |
| 5002B | 24 | | G2 | AG | 3-0 | 27-58-31 | D03258B | | K13 | | | D41381J | 6 | | 115-199 |
| 5002R | 24 | | G2 | AG | 0-0 | 27-58-31 | D03258B | | J13 | | | D41381J | 7 | | ALL |
| 5002Z | | | | AG | 0-0 | 27-58-31 | GD02084 | | ST.. | 2 | | D41381J | 8 | | ALL |
| 5003B | 24 | | G2 | BB | 3-1 | 34-22-39 | D00223B | | G03 | | | TB0185Y | C004 | BJ | 001-099 |
| 5003B | 24 | | G2 | AH | 3-0 | 34-33-31 | D00223B | | G03 | | | TB0185Y | C004 | BJ | 115-199 |
| 5003R | 24 | | G2 | BB | 0-0 | 34-22-39 | D00223B | | G02 | | | TB0185Y | A005 | BJ | 001-099 |
| 5003R | 24 | | G2 | AH | 0-0 | 34-33-31 | D00223B | | G02 | | | TB0185Z | 5 | BJ | 115-199 |
| 5003Z | | | | BB | 0-0 | 34-22-39 | D00223B | | DED | | | GD02083 | ST.. | 2 | 001-099 |
| 5003Z | | | | AH | 0-0 | 34-33-31 | D00223B | | DED | | | GD02083 | ST.. | 2 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 55

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1286 | 286N1286 | | | E5-3 SHELF (continued) | | | | | | | | | | | |
| 5004B | 24 | G2 | AJ | | 2-9 | 24-22-12 | D00550A | B12 | | | D41329J | 17 | | | 001-099 |
| 5004B | 24 | G2 | AJ | | 3-0 | 24-22-12 | D00550A | B12 | | | D41329J | 17 | | | 115-199 |
| 5004R | 24 | G2 | AJ | | 0-0 | 24-22-12 | D00550A | A12 | | | D41329J | 18 | | | ALL |
| 5004Z | | | AJ | | 0-0 | 24-22-12 | D00550A | | | FL | D41329J | 19 | | | ALL |
| 5005B | 24 | G2 | AM | | 2-6 | 24-22-22 | D00550A | D12 | | | D41750J | 19 | | | 001-099 |
| 5005B | 24 | G2 | AM | | 3-0 | 24-22-22 | D00550A | D12 | | | D41750J | 19 | | | 115-199 |
| 5005R | 24 | G2 | AM | | 0-0 | 24-22-22 | D00550A | C12 | | | D41750J | 20 | | | ALL |
| 5005Z | | | AM | | 0-0 | 24-22-22 | D00550A | | | FL | D41750J | 21 | | | ALL |
| 5006B | 24 | G2 | AH | | 2-5 | 34-22-39 | TB0185Y | C004 | BJ | | D41419J | 5 | | | 001-099 |
| 5006B | 24 | G2 | AI | | 3-0 | 34-22-39 | D41419J | 5 | | | TB0185Y | C004 | BJ | | 115-199 |
| 5006R | 24 | G2 | AH | | 0-0 | 34-22-39 | TB0185Y | A005 | BJ | | D41419J | 4 | | | 001-099 |
| 5006R | 24 | G2 | AI | | 0-0 | 34-22-39 | D41419J | 4 | | | TB0185Z | 5 | BJ | | 115-199 |
| 5006Z | | | AH | | 0-0 | 34-22-39 | GD02083 | ST.. | 2 | | D41419J | 6 | | | 001-099 |
| 5006Z | | | AI | | 0-0 | 34-22-39 | D41419J | 6 | | | GD02083 | ST.. | 2 | | 115-199 |
| 5007B | 24 | G2 | AO | | 2-5 | 31-31-43 | D41419J | 17 | | | TB0185Y | C004 | BJ | | 001-099 |
| 5007B | 24 | G2 | AB | | 3-0 | 31-31-22 | D41419J | 17 | | | TB0185Y | C004 | BJ | | 115-199 |
| 5007R | 24 | G2 | AO | | 0-0 | 31-31-43 | D41419J | 16 | | | TB0185Y | A005 | BJ | | 001-099 |
| 5007R | 24 | G2 | AB | | 0-0 | 31-31-22 | D41419J | 16 | | | TB0185Z | 5 | BJ | | 115-199 |
| 5007Z | | | AO | | 0-0 | 31-31-43 | D41419J | 18 | | | GD02083 | ST.. | 2 | | 001-099 |
| 5007Z | | | AB | | 0-0 | 31-31-22 | D41419J | 18 | | | GD02083 | ST.. | 2 | | 115-199 |
| 5009B | 24 | G2 | BE | | 2-10 | 22-12-31 | D41419J | 9 | | | D00223B | B03 | | | 001-099 |
| 5009B | 24 | G2 | BE | | 3-0 | 22-12-31 | D41419J | 9 | | | D00223B | B03 | | | 115-199 |
| 5009R | 24 | G2 | BE | | 0-0 | 22-12-31 | D41419J | 8 | | | D00223B | B02 | | | ALL |
| 5009Z | | | BE | | 0-0 | 22-12-31 | D41419J | 10 | | | GD02088 | ST.. | 2 | | ALL |
| 5011B | 24 | G2 | BP | | 2-4 | 24-41-11 | D41381J | 50 | | | D00550A | B13 | | | 001-099 |
| 5011B | 24 | G2 | BP | | 3-0 | 24-41-11 | D01850A | B12 | | | D00550A | B13 | | | 115-199 |
| 5011R | 24 | G2 | BP | | 0-0 | 24-41-11 | D41381J | 49 | | | D00550A | A13 | | | 001-099 |
| 5011R | 24 | G2 | BP | | 0-0 | 24-41-11 | D01850A | A12 | | | D00550A | A13 | | | 115-199 |
| 5011Z | | | BP | | 0-0 | 24-41-11 | D41381J | 51 | | | D00550A | | | FL | 001-099 |
| 5011Z | | | BP | | 0-0 | 24-41-11 | D01850A | B11 | | | D00550A | | | FL | 115-199 |
| 5012B | 24 | G2 | AC | | 3-0 | 31-51-34 | D41463J | 22 | | | TB0185Y | C004 | BJ | | 009 |
| 5012B | 24 | G2 | AO | | 3-0 | 31-51-34 | D41419J | 22 | | | TB0185Y | C004 | BJ | | 115-199 |
| 5012R | 24 | G2 | AC | | 0-0 | 31-51-34 | D41463J | 21 | | | TB0185Y | A005 | BJ | | 009 |
| 5012R | 24 | G2 | AO | | 0-0 | 31-51-34 | D41419J | 21 | | | TB0185Z | 5 | BJ | | 115-199 |
| 5012Z | | | AC | | 0-0 | 31-51-34 | D41463J | 23 | | | GD02083 | ST.. | 2 | | 009 |
| 5012Z | | | AO | | 0-0 | 31-51-34 | D41419J | 23 | | | GD02083 | ST.. | 2 | | 115-199 |
| 5051B | 22 | GU | A | | 3-0 | 34-46-12 | D41419J | 28 | | | TB0185Y | C004 | BJ | | 002 |
| 5051R | 22 | GU | A | | 0-0 | 34-46-12 | D41419J | 27 | | | TB0185Y | A005 | BJ | | 002 |
| 5051Z | | | A | | 0-0 | 34-46-12 | D41419J | 29 | | | GD02083 | ST.. | 2 | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 56

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice Effectivity |
| W1286 | 286N1286 | | | E5-3 SHELF (continued) | | | | | | | | | | |
| FRAA | | | | | 0-0 | 24-41-11 | D00550A | | | FL | D00550A | A14 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1280

Page 57 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1310 | 286N1310 | | | RIGHT WINDSHIELD HEATER CONTROL-E1-1 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 3-0 | 30-41-12 | D41600J | | 1 | | D02290A | 11 | | | ALL |
| 0002 | 22 | | GA | | 3-0 | 30-41-11 | D02290A | | 12 | | D41872J | 6 | | | ALL |
| 0004 | 20 | | GA | | 3-0 | 30-41-12 | D41600J | | 7 | | D02290A | 16 | | | ALL |
| 0005 | 22 | | GA | | 3-0 | 30-41-12 | D41872J | | 1 | | D02290A | 6 | | | ALL |
| 0006 | 22 | | GA | | 3-0 | 30-41-12 | D41872J | | 3 | | D02290A | 7 | | | ALL |
| 0007 | 22 | | GA | | 3-0 | 30-41-12 | D41872J | | 2 | | D02290A | 8 | | | ALL |
| 0008 | 22 | | GA | | 3-0 | 30-41-12 | D41872J | | 4 | | D02290A | 9 | | | ALL |
| 0009 | 22 | | GA | | 3-0 | 30-41-12 | D41872J | | 5 | | D02290A | 10 | | | ALL |
| 0010 | 20 | | GA | | 3-0 | 30-41-12 | D41756J | | 2 | | D02290A | 2 | | | ALL |
| 0011 | 20 | | GA | | 3-0 | 30-41-12 | D41756J | | 1 | | D02290A | 1 | | | ALL |
| 0012 | 20 | | GA | | 3-0 | 30-41-12 | D02290A | | 3 | | GD02127 | AC.. | 2 | | ALL |
| 0013 | 20 | | GA | | 3-0 | 30-41-12 | D02290A | | 4 | | GD02127 | DC.. | 2 | | ALL |
| 0014 | 20 | | GA | | 3-0 | 30-41-12 | D02290A | | 5 | | GD02127 | DC.. | 2 | | ALL |
| 0015 | 12 | | GA | | 2-0 | 30-41-12 | D02290B | | 3 | | GD02379 | AC.. | E | | ALL |
| 0016 | 12 | | GA | | 2-0 | 30-41-12 | D02290B | | 6 | | GD02381 | ST.. | E | | ALL |
| 0019 | 20 | | GA | | 4-0 | 30-41-12 | GD02127 | ST.. | 2 | | D41600J | | | AA | 001-099 |
| 0019 | 20 | | GA | | 2-0 | 30-41-12 | GD02127 | ST.. | 2 | | TB0107X | REF | | AB | 115-199 |
| 0020 | 20 | | GA | | 4-0 | 30-41-12 | GD02127 | ST.. | 2 | | D41600J | | | AC | 001-099 |
| 0020 | 20 | | GA | | 2-0 | 30-41-12 | GD02127 | ST.. | 2 | | TB0107X | REF | | AD | 115-199 |
| 0021 | 20 | | GA | | 4-0 | 30-41-12 | GD02127 | ST.. | 2 | | D41604J | | | AE | 001-099 |
| 0021 | 20 | | GA | | 2-0 | 30-41-12 | GD02127 | ST.. | 2 | | TB0107X | REF | | AF | 115-199 |
| 0024 | 20 | | GA | | 3-0 | 24-25-12 | D07672 | | C | | D41440J | 1 | | | 003-099 |
| 0025 | 20 | | GA | | 3-0 | 24-25-12 | D07672 | | B | | D41440J | 2 | | | 003-099 |
| 0026 | 20 | | GA | | 3-0 | 24-25-12 | D07672 | | A | | D41440J | 3 | | | 003-099 |
| 0027 | 16 | | GA | | 2-0 | 24-25-12 | D07672 | | E | | GD02379 | AC.. | E | | 003-099 |
| 0028 | 08 | | GA | | 1-7 | 24-25-12 | D07672 | | H | | GD04034 | DC.. | E | | 003-099 |
| 0029 | 08 | | GA | | 1-8 | 24-31-11 | D07672 | | D | | TB0012 | 1 | E | | 003-099 |
| 2001B | 12 | | GB | AA | 3-0 | 30-41-12 | D41602J | | 1 | | D02290B | 4 | | | ALL |
| 2001R | 12 | | GB | AA | 0-0 | 30-41-12 | D41602J | | 2 | | D02290B | 5 | | | ALL |
| 2002B | 12 | | GB | AB | 3-0 | 30-41-12 | D41756J | | 4 | | D02290B | 1 | | | ALL |
| 2002R | 12 | | GB | AB | 0-0 | 30-41-12 | D41756J | | 5 | | D02290B | 2 | | | ALL |
| 2501B | 22 | | GU | AC | 3-0 | 30-41-12 | D02290A | | 13 | | TB0107X | A002 | BJ | | 115-199 |
| 2501R | 22 | | GU | AC | 0-0 | 30-41-12 | D02290A | | 14 | | TB0107X | B002 | BJ | | 115-199 |
| 2501Z | | | | AC | 0-0 | 30-41-12 | D02290A | DED | | | TB0107X | REF | | AB | 115-199 |
| 2502B | 22 | | GU | AD | 3-0 | 30-41-12 | D41600J | | 4 | | D02290A | 13 | | | 001-099 |
| 2502B | 22 | | GU | AD | 4-0 | 30-41-12 | D41600J | | 4 | | TB0107X | A002 | BJ | | 115-199 |
| 2502R | 22 | | GU | AD | 0-0 | 30-41-12 | D41600J | | 5 | | D02290A | 14 | | | 001-099 |
| 2502R | 22 | | GU | AD | 0-0 | 30-41-12 | D41600J | | 5 | | TB0107X | B002 | BJ | | 115-199 |
| 2502Z | | | | AD | 0-0 | 30-41-12 | D41600J | | | AA | D02290A | DED | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1310

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1310 | 286N1310 | | | RIGHT WINDSHIELD HEATER CONTROL-E1-1 (continued) | | | | | | | | | | | |
| 2502Z | | | | AD | 0-0 | 30-41-12 | D41600J | | | AA | TB0107X | REF | | AB | 115-199 |
| 2503B | 22 | GU | AE | | 4-0 | 30-41-12 | D41600J | 2 | | | TB0107X | C002 | BJ | | 115-199 |
| 2503R | 22 | GU | AE | | 0-0 | 30-41-12 | D41600J | 3 | | | TB0107X | D002 | BJ | | 115-199 |
| 2503Z | | | AE | | 0-0 | 30-41-12 | D41600J | | | AA | TB0107X | REF | | AB | 115-199 |
| 2504B | 22 | GU | AF | | 3-0 | 30-41-12 | D02290A | 17 | | | TB0107X | A003 | BJ | | 115-199 |
| 2504R | 22 | GU | AF | | 0-0 | 30-41-12 | D02290A | 18 | | | TB0107X | B003 | BJ | | 115-199 |
| 2504Z | | | AF | | 0-0 | 30-41-12 | D02290A | DED | | | TB0107X | REF | | AD | 115-199 |
| 2505B | 22 | GU | AG | | 3-0 | 30-41-12 | D41600J | 8 | | | D02290A | 17 | | | 001-099 |
| 2505B | 22 | GU | AG | | 4-0 | 30-41-12 | D41600J | 8 | | | TB0107X | A003 | BJ | | 115-199 |
| 2505R | 22 | GU | AG | | 0-0 | 30-41-12 | D41600J | 9 | | | D02290A | 18 | | | 001-099 |
| 2505R | 22 | GU | AG | | 0-0 | 30-41-12 | D41600J | 9 | | | TB0107X | B003 | BJ | | 115-199 |
| 2505Z | | | AG | | 0-0 | 30-41-12 | D41600J | | | AC | D02290A | DED | | | 001-099 |
| 2505Z | | | AG | | 0-0 | 30-41-12 | D41600J | | | AC | TB0107X | REF | | AD | 115-199 |
| 2506B | 22 | GU | AH | | 4-0 | 30-41-12 | D41600J | 10 | | | TB0107X | C003 | BJ | | 115-199 |
| 2506R | 22 | GU | AH | | 0-0 | 30-41-12 | D41600J | 11 | | | TB0107X | D003 | BJ | | 115-199 |
| 2506Z | | | AH | | 0-0 | 30-41-12 | D41600J | | | AC | TB0107X | REF | | AD | 115-199 |
| 2507B | 22 | GU | AI | | 3-0 | 30-41-12 | D02290A | 19 | | | TB0107X | A001 | BJ | | 115-199 |
| 2507R | 22 | GU | AI | | 0-0 | 30-41-12 | D02290A | 20 | | | TB0107X | B001 | BJ | | 115-199 |
| 2507Z | | | AI | | 0-0 | 30-41-12 | D02290A | DED | | | TB0107X | REF | | AF | 115-199 |
| 2508B | 22 | GU | AJ | | 3-0 | 30-41-12 | D41604J | 2 | | | D02290A | 19 | | | 001-099 |
| 2508B | 22 | GU | AJ | | 3-0 | 30-41-12 | D41604J | 2 | | | TB0107X | A001 | BJ | | 115-199 |
| 2508R | 22 | GU | AJ | | 0-0 | 30-41-12 | D41604J | 3 | | | D02290A | 20 | | | 001-099 |
| 2508R | 22 | GU | AJ | | 0-0 | 30-41-12 | D41604J | 3 | | | TB0107X | B001 | BJ | | 115-199 |
| 2508Z | | | AJ | | 0-0 | 30-41-12 | D41604J | | | AE | D02290A | DED | | | 001-099 |
| 2508Z | | | AJ | | 0-0 | 30-41-12 | D41604J | | | AE | TB0107X | REF | | AF | 115-199 |
| 2509B | 22 | GU | AK | | 3-0 | 30-41-12 | D41604J | 4 | | | TB0107X | C001 | BJ | | 115-199 |
| 2509R | 22 | GU | AK | | 0-0 | 30-41-12 | D41604J | 5 | | | TB0107X | D001 | BJ | | 115-199 |
| 2509Z | | | AK | | 0-0 | 30-41-12 | D41604J | | | AE | TB0107X | REF | | AF | 115-199 |
| FRAA | | | | | 0-0 | 30-41-12 | D41600J | 6 | | | D41600J | | | AA | ALL |
| FRAC | | | | | 0-0 | 30-41-12 | D41600J | 12 | | | D41600J | | | AC | ALL |
| FRAE | | | | | 0-0 | 30-41-12 | D41604J | 6 | | | D41604J | | | AE | ALL |

WIRE LIST

D280N032

91-21-11

Section W1310

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1320 286N1320 LEFT WINDSHEILD HEATER CONTROL-E1-2 | | | | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 3-0 | 30-41-11 | D41596J | | | | D02304A | 11 | | | ALL |
| 0002 | 22 | | GA | | 2-0 | 30-41-11 | D02304A | | | | TB0106Y | A005 | BJ | | 001-099 |
| 0002 | 22 | | GA | | 2-1 | 30-41-11 | D02304A | | | | TB0106Y | A005 | BJ | | 115-199 |
| 0004 | 20 | | GA | | 3-0 | 30-41-11 | D41596J | | | | D02304A | 16 | | | ALL |
| 0005 | 22 | | GA | | 3-0 | 30-41-11 | D41874J | | | | D02304A | 6 | | | 001-099 |
| 0005 | 22 | | GA | | 2-10 | 30-41-11 | D41874J | | | | D02304A | 6 | | | 115-199 |
| 0006 | 22 | | GA | | 3-0 | 30-41-11 | D41874J | | | | D02304A | 7 | | | 001-099 |
| 0006 | 22 | | GA | | 2-10 | 30-41-11 | D41874J | | | | D02304A | 7 | | | 115-199 |
| 0007 | 22 | | GA | | 3-0 | 30-41-11 | D41874J | | | | D02304A | 8 | | | 001-099 |
| 0007 | 22 | | GA | | 2-10 | 30-41-11 | D41874J | | | | D02304A | 8 | | | 115-199 |
| 0008 | 22 | | GA | | 3-0 | 30-41-11 | D41874J | | | | D02304A | 9 | | | 001-099 |
| 0008 | 22 | | GA | | 2-10 | 30-41-11 | D41874J | | | | D02304A | 9 | | | 115-199 |
| 0009 | 22 | | GA | | 3-0 | 30-41-11 | D41874J | | | | D02304A | 10 | | | 001-099 |
| 0009 | 22 | | GA | | 2-10 | 30-41-11 | D41874J | | | | D02304A | 10 | | | 115-199 |
| 0010 | 20 | | GA | | 2-2 | 30-41-11 | D41914J | | | | D02304A | 2 | | | ALL |
| 0011 | 20 | | GA | | 2-2 | 30-41-11 | D41914J | | | | D02304A | 1 | | | ALL |
| 0012 | 20 | | GA | | 2-1 | 30-41-11 | D02304A | | | | GD02121 | AC.. | 2 | | ALL |
| 0013 | 20 | | GA | | 2-1 | 30-41-11 | D02304A | | | | GD02121 | DC.. | 2 | | ALL |
| 0014 | 20 | | GA | | 2-1 | 30-41-11 | D02304A | | | | GD02121 | DC.. | 2 | | ALL |
| 0015 | 12 | | GA | | 1-9 | 30-41-11 | D02304B | | | | GD02383 | AC.. | E | | ALL |
| 0016 | 12 | | GA | | 1-9 | 30-41-11 | D02304B | | | | GD02385 | ST.. | E | | ALL |
| 0019 | 20 | | GA | | 2-11 | 30-41-11 | GD02121 | ST.. | 2 | | D41596J | | | AA | 001-099 |
| 0019 | 20 | | GA | | 1-8 | 30-41-11 | GD02121 | ST.. | 2 | | TB0106X | REF | | AB | 115-199 |
| 0020 | 20 | | GA | | 2-11 | 30-41-11 | GD02121 | ST.. | 2 | | D41596J | | | AC | 001-099 |
| 0020 | 20 | | GA | | 1-8 | 30-41-11 | GD02121 | ST.. | 2 | | TB0106X | REF | | AD | 115-199 |
| 0021 | 20 | | GA | | 2-0 | 30-41-11 | GD02121 | ST.. | 2 | | D41594J | | | AE | 001-099 |
| 0021 | 20 | | GA | | 1-8 | 30-41-11 | GD02121 | ST.. | 2 | | TB0106X | REF | | AF | 115-199 |
| 0022 | 22 | | GA | | 2-10 | 30-41-11 | D41874J | | | | TB0106Y | A005 | BJ | | 001-099 |
| 0022 | 22 | | GA | | 2-9 | 30-41-11 | D41874J | | | | TB0106Y | A005 | BJ | | 115-199 |
| 0023 | 22 | | GA | | 2-10 | 30-41-11 | D41874J | | | | TB0106Y | A005 | BJ | | 001-099 |
| 0023 | 22 | | GA | | 2-9 | 30-41-11 | D41874J | | | | TB0106Y | A005 | BJ | | 115-199 |
| 2001B | 12 | | GB | AA | 2-2 | 30-41-11 | D41592J | | | | D02304B | 4 | | | ALL |
| 2001R | 12 | | GB | AA | 0-0 | 30-41-11 | D41592J | | | | D02304B | 5 | | | ALL |
| 2002B | 12 | | GB | AB | 2-2 | 30-41-11 | D41914J | | | | D02304B | 2 | | | ALL |
| 2002R | 12 | | GB | AB | 0-0 | 30-41-11 | D41914J | | | | D02304B | 1 | | | ALL |
| 2501B | 22 | | GU | AC | 2-1 | 30-41-11 | D02304A | | | | TB0106X | A001 | BJ | | 115-199 |
| 2501R | 22 | | GU | AC | 0-0 | 30-41-11 | D02304A | | | | TB0106X | B001 | BJ | | 115-199 |
| 2501Z | | | | AC | 0-0 | 30-41-11 | D02304A | DED | | | TB0106X | REF | | AB | 115-199 |
| 2502B | 22 | | GU | AD | 3-0 | 30-41-11 | D41596J | | | | D02304A | 13 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1320

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | | To | | | | | Effectivity |
|------------|-------------|----|-------|---|---------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1320 | 286N1320 | | | LEFT WINDSHIELD HEATER CONTROL-E1-2 (continued) | | | | | | | | | | | | |
| 2502B | 22 | GU | AD | | 2-11 | 30-41-11 | D41596J | 4 | | | | TB0106X | A001 | BJ | | 115-199 |
| 2502R | 22 | GU | AD | | 0-0 | 30-41-11 | D41596J | 5 | | | | D02304A | 14 | | | 001-099 |
| 2502R | 22 | GU | AD | | 0-0 | 30-41-11 | D41596J | 5 | | | | TB0106X | B001 | BJ | | 115-199 |
| 2502Z | | | AD | | 0-0 | 30-41-11 | D41596J | | | | AA | D02304A | DED | | | 001-099 |
| 2502Z | | | AD | | 0-0 | 30-41-11 | D41596J | | | | AA | TB0106X | REF | | AB | 115-199 |
| 2503B | 22 | GU | AE | | 2-11 | 30-41-11 | D41596J | 2 | | | | TB0106X | C001 | BJ | | 115-199 |
| 2503R | 22 | GU | AE | | 0-0 | 30-41-11 | D41596J | 3 | | | | TB0106X | D001 | BJ | | 115-199 |
| 2503Z | | | AE | | 0-0 | 30-41-11 | D41596J | | | | AA | TB0106X | REF | | AB | 115-199 |
| 2504B | 22 | GU | AF | | 2-1 | 30-41-11 | D02304A | 17 | | | | TB0106X | A002 | BJ | | 115-199 |
| 2504R | 22 | GU | AF | | 0-0 | 30-41-11 | D02304A | 18 | | | | TB0106X | B002 | BJ | | 115-199 |
| 2504Z | | | AF | | 0-0 | 30-41-11 | D02304A | DED | | | | TB0106X | REF | | AD | 115-199 |
| 2505B | 22 | GU | AG | | 3-0 | 30-41-11 | D41596J | 8 | | | | D02304A | 17 | | | 001-099 |
| 2505B | 22 | GU | AG | | 2-11 | 30-41-11 | D41596J | 8 | | | | TB0106X | A002 | BJ | | 115-199 |
| 2505R | 22 | GU | AG | | 0-0 | 30-41-11 | D41596J | 9 | | | | D02304A | 18 | | | 001-099 |
| 2505R | 22 | GU | AG | | 0-0 | 30-41-11 | D41596J | 9 | | | | TB0106X | B002 | BJ | | 115-199 |
| 2505Z | | | AG | | 0-0 | 30-41-11 | D41596J | | | | AC | D02304A | DED | | | 001-099 |
| 2505Z | | | AG | | 0-0 | 30-41-11 | D41596J | | | | AC | TB0106X | REF | | AD | 115-199 |
| 2506B | 22 | GU | AH | | 2-11 | 30-41-11 | D41596J | 10 | | | | TB0106X | C002 | BJ | | 115-199 |
| 2506R | 22 | GU | AH | | 0-0 | 30-41-11 | D41596J | 11 | | | | TB0106X | D002 | BJ | | 115-199 |
| 2506Z | | | AH | | 0-0 | 30-41-11 | D41596J | | | | AC | TB0106X | REF | | AD | 115-199 |
| 2507B | 22 | GU | AI | | 2-1 | 30-41-11 | D02304A | 19 | | | | TB0106X | A003 | BJ | | 115-199 |
| 2507R | 22 | GU | AI | | 0-0 | 30-41-11 | D02304A | 20 | | | | TB0106X | B003 | BJ | | 115-199 |
| 2507Z | | | AI | | 0-0 | 30-41-11 | D02304A | DED | | | | TB0106X | REF | | AF | 115-199 |
| 2508B | 22 | GU | AJ | | 2-0 | 30-41-11 | D41594J | 2 | | | | D02304A | 19 | | | 001-099 |
| 2508B | 22 | GU | AJ | | 2-0 | 30-41-11 | D41594J | 2 | | | | TB0106X | A003 | BJ | | 115-199 |
| 2508R | 22 | GU | AJ | | 0-0 | 30-41-11 | D41594J | 3 | | | | D02304A | 20 | | | 001-099 |
| 2508R | 22 | GU | AJ | | 0-0 | 30-41-11 | D41594J | 3 | | | | TB0106X | B003 | BJ | | 115-199 |
| 2508Z | | | AJ | | 0-0 | 30-41-11 | D41594J | | | | AE | D02304A | DED | | | 001-099 |
| 2508Z | | | AJ | | 0-0 | 30-41-11 | D41594J | | | | AE | TB0106X | REF | | AF | 115-199 |
| 2509B | 22 | GU | AK | | 2-0 | 30-41-11 | D41594J | 4 | | | | TB0106X | C003 | BJ | | 115-199 |
| 2509R | 22 | GU | AK | | 0-0 | 30-41-11 | D41594J | 5 | | | | TB0106X | D003 | BJ | | 115-199 |
| 2509Z | | | AK | | 0-0 | 30-41-11 | D41594J | | | | AE | TB0106X | REF | | AF | 115-199 |
| FRAA | | | | | 0-0 | 30-41-11 | D41596J | 6 | | | | D41596J | | | AA | ALL |
| FRAC | | | | | 0-0 | 30-41-11 | D41596J | 12 | | | | D41596J | | | AC | ALL |
| FRAE | | | | | 0-0 | 30-41-11 | D41594J | 6 | | | | D41594J | | | AE | ALL |

WIRE LIST

D280N032

91-21-11

Section W1320

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1330 | 286N1330 | | | | E3-3 SHELF (ELECTRICAL) | | | | | | | | | | | | |
| 0001 | 22 | | GA | | 2-1 | 21-51-12 | D02964C | | | 2 | | D40656J | 1 | | | 001-099 | |
| 0002 | 20 | | GA | | 2-9 | 21-51-12 | D02964C | | | 4 | | GD03366 | AC.. | 2 | | 001-099 | |
| 0003 | 24 | | GK | | 2-9 | 21-51-12 | D02964C | | | 3 | | GD03366 | ST.. | 2 | | 001-099 | |
| 0007 | 24 | | GK | | 2-2 | 21-51-12 | D02964B | | | C13 | | D40656J | 3 | | | 001-099 | |
| 0008 | 24 | | GK | | 2-2 | 21-51-12 | D02964B | | | C15 | | D40656J | 4 | | | 001-099 | |
| 0009 | 24 | | GK | | 2-2 | 21-51-12 | D02964B | | | B13 | | D40656J | 5 | | | 001-099 | |
| 0010 | 24 | | GK | | 2-2 | 21-51-12 | D02964B | | | B15 | | D40656J | 6 | | | 001-099 | |
| 0011 | 24 | | GK | | 2-2 | 21-51-12 | D02964B | | | A13 | | D40656J | 7 | | | 001-099 | |
| 0012 | 24 | | GK | | 2-2 | 21-51-12 | D02964B | | | A15 | | D40656J | 8 | | | 001-099 | |
| 0013 | 24 | | GK | | 2-2 | 21-51-12 | D02964B | | | D07 | | D40656J | 9 | | | 001-099 | |
| 0020 | 24 | | GK | | 2-2 | 21-51-15 | D02964B | | | C05 | | D40656J | 53 | | | 001-099 | |
| 0024 | 24 | | GK | | 3-0 | 21-51-12 | D02964A | | | C15 | | GD03366 | DC.. | 2 | | 001-099 | |
| 0025 | 24 | | GK | | 2-2 | 21-51-15 | D02964B | | | C07 | | D40656J | 42 | | | 001-099 | |
| 0026 | 24 | | GK | | 2-2 | 21-51-15 | D02964B | | | B09 | | D40656J | 43 | | | 001-099 | |
| 0027 | 24 | | GK | | 2-1 | 21-51-24 | D04130B | | | A15 | | D40670J | 1 | | | 001-099 | |
| 0028 | 24 | | GK | | 2-10 | 21-51-24 | D04130B | | | C15 | | GD03366 | AC.. | 2 | | 001-099 | |
| 0029 | 24 | | GK | | 2-10 | 21-51-24 | D04130B | | | B14 | | GD03366 | DC.. | 2 | | 001-099 | |
| 0030 | 24 | | GK | | 2-6 | 21-61-11 | D02558B | | | A09 | | D40670J | 11 | | | 001-099 | |
| 0031 | 24 | | GK | | 2-6 | 21-61-11 | D02558B | | | A15 | | D40670J | 12 | | | 001-099 | |
| 0032 | 24 | | GK | | 2-6 | 21-61-11 | D02558B | | | A13 | | D40670J | 13 | | | 001-099 | |
| 0033 | 24 | | GK | | 2-6 | 21-61-11 | D02558B | | | A12 | | D40670J | 14 | | | 001-099 | |
| 0034 | 24 | | GK | | 2-6 | 21-61-11 | D02558B | | | A11 | | D40670J | 15 | | | 001-099 | |
| 0038 | 24 | | GK | | 2-6 | 21-61-21 | D02558B | | | B09 | | D40670J | 26 | | | 001-099 | |
| 0039 | 24 | | GK | | 2-6 | 21-61-21 | D02558B | | | B15 | | D40670J | 27 | | | 001-099 | |
| 0040 | 24 | | GK | | 2-6 | 21-61-21 | D02558B | | | B13 | | D40670J | 28 | | | 001-099 | |
| 0041 | 24 | | GK | | 2-6 | 21-61-21 | D02558B | | | B12 | | D40670J | 29 | | | 001-099 | |
| 0042 | 24 | | GK | | 2-6 | 21-61-21 | D02558B | | | B11 | | D40670J | 30 | | | 001-099 | |
| 0050 | 24 | | GK | | 2-7 | 21-61-31 | D02558B | | | C11 | | D40844J | 5 | | | 001-099 | |
| 0051 | 24 | | GK | | 2-7 | 21-61-31 | D02558B | | | C09 | | D40844J | 9 | | | 001-099 | |
| 0052 | 24 | | GK | | 2-7 | 21-61-31 | D02558B | | | C12 | | D40844J | 6 | | | 001-099 | |
| 0053 | 24 | | GK | | 2-7 | 21-61-31 | D02558B | | | C13 | | D40844J | 7 | | | 001-099 | |
| 0054 | 24 | | GK | | 2-7 | 21-61-31 | D02558B | | | C15 | | D40844J | 8 | | | 001-099 | |
| 0055 | 22 | | GA | | 1-11 | 21-61-51 | D02558C | | | 4 | | GD03366 | AC.. | 2 | | 001-099 | |
| 0056 | 24 | | GK | | 2-6 | 21-61-51 | D02558C | | | 2 | | D40846J | 3 | | | 001-099 | |
| 0057 | 24 | | GK | | 2-8 | 21-61-51 | D02558B | | | C03 | | D40846J | 16 | | | 001-099 | |
| 0058 | 22 | | GA | | 2-2 | 21-61-51 | D02558A | | | C15 | | GD03366 | DC.. | 2 | | 001-099 | |
| 0059 | 24 | | GK | | 3-0 | 21-51-14 | D04130A | | | C15 | | GD03366 | AC.. | 2 | | 001-099 | |
| 0060 | 24 | | GK | | 3-0 | 21-51-14 | D04130A | | | B14 | | GD03366 | DC.. | 2 | | 001-099 | |
| 0061 | 24 | | GK | | 2-9 | 21-51-14 | D04130C | | | 3 | | GD03366 | ST.. | 2 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1330

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1330 | 286N1330 | | | E3-3 SHELF (ELECTRICAL) (continued) | | | | | | | | | | |
| 0062 | 22 | GA | | 1-11 | 21-61-51 | D02558C | 3 | | | GD03366 | ST.. | 2 | | 001-099 |
| 0171 | 24 | GK | | 2-3 | 21-51-14 | D04130A | A15 | | | D40656J | 12 | | | 001-099 |
| 2001B | 24 | GL | DA | 2-2 | 21-51-12 | D02964B | B02 | | | D40656J | 11 | | | 001-099 |
| 2001R | 24 | GL | DA | 0-0 | 21-51-12 | D02964B | B01 | | | D40656J | 10 | | | 001-099 |
| 2002B | 24 | GL | AG | 2-2 | 21-51-14 | D02964B | C01 | | | D40656J | 40 | | | 001-099 |
| 2002R | 24 | GL | AG | 0-0 | 21-51-14 | D02964B | C02 | | | D40656J | 41 | | | 001-099 |
| 2003B | 24 | GL | AH | 2-4 | 21-51-15 | D02964A | D04 | | | D40656J | 44 | | | 001-099 |
| 2003R | 24 | GL | AH | 0-0 | 21-51-15 | D02964A | D05 | | | D40656J | 45 | | | 001-099 |
| 2004B | 24 | GL | AI | 2-1 | 21-51-24 | D04130B | B12 | | | D40670J | 3 | | | 001-099 |
| 2004R | 24 | GL | AI | 0-0 | 21-51-24 | D04130B | A12 | | | D40670J | 2 | | | 001-099 |
| 2005B | 24 | GL | AJ | 2-1 | 21-51-24 | D04130B | B09 | | | D40670J | 5 | | | 001-099 |
| 2005R | 24 | GL | AJ | 0-0 | 21-51-24 | D04130B | A09 | | | D40670J | 4 | | | 001-099 |
| 2006B | 24 | GL | AK | 2-1 | 21-51-24 | D04130B | B10 | | | D40670J | 7 | | | 001-099 |
| 2006R | 24 | GL | AK | 0-0 | 21-51-24 | D04130B | A10 | | | D40670J | 6 | | | 001-099 |
| 2007B | 24 | GL | AM | 2-7 | 21-61-11 | D02558A | A07 | | | D40670J | 20 | | | 001-099 |
| 2007R | 24 | GL | AM | 0-0 | 21-61-11 | D02558A | A06 | | | D40670J | 19 | | | 001-099 |
| 2008B | 24 | GL | AN | 2-7 | 21-61-11 | D02558A | A05 | | | D40670J | 22 | | | 001-099 |
| 2008R | 24 | GL | AN | 0-0 | 21-61-11 | D02558A | A04 | | | D40670J | 21 | | | 001-099 |
| 2009B | 24 | GL | AP | 2-7 | 21-61-21 | D02558A | B07 | | | D40670J | 35 | | | 001-099 |
| 2009R | 24 | GL | AP | 0-0 | 21-61-21 | D02558A | B06 | | | D40670J | 34 | | | 001-099 |
| 2010B | 24 | GL | AQ | 2-9 | 21-61-21 | D02558A | B05 | | | D40846J | 22 | | | 001-099 |
| 2010R | 24 | GL | AQ | 0-0 | 21-61-21 | D02558A | B04 | | | D40846J | 21 | | | 001-099 |
| 2011B | 24 | GL | AS | 2-8 | 21-61-31 | D02558A | C07 | | | D40844J | 14 | | | 001-099 |
| 2011R | 24 | GL | AS | 0-0 | 21-61-31 | D02558A | C06 | | | D40844J | 13 | | | 001-099 |
| 2012B | 24 | GL | AT | 2-8 | 21-61-31 | D02558A | C05 | | | D40844J | 15 | | | 001-099 |
| 2012R | 24 | GL | AT | 0-0 | 21-61-31 | D02558A | C04 | | | D40844J | 16 | | | 001-099 |
| 2013B | 24 | GL | AV | 2-8 | 21-61-51 | D02558B | D03 | | | D40846J | 2 | | | 001-099 |
| 2013R | 24 | GL | AV | 0-0 | 21-61-51 | D02558B | D04 | | | D40846J | 1 | | | 001-099 |
| 2014B | 24 | GL | AW | 2-8 | 21-61-51 | D02558B | B05 | | | D40846J | 5 | | | 001-099 |
| 2014R | 24 | GL | AW | 0-0 | 21-61-51 | D02558B | B06 | | | D40846J | 4 | | | 001-099 |
| 2015B | 24 | GL | AX | 2-8 | 21-61-51 | D02558B | B04 | | | D40846J | 7 | | | 001-099 |
| 2015R | 24 | GL | AX | 0-0 | 21-61-51 | D02558B | B03 | | | D40846J | 6 | | | 001-099 |
| 2016B | 24 | GL | AY | 2-8 | 21-61-51 | D02558B | B02 | | | D40846J | 9 | | | 001-099 |
| 2016R | 24 | GL | AY | 0-0 | 21-61-51 | D02558B | B01 | | | D40846J | 8 | | | 001-099 |
| 2017B | 24 | GL | AZ | 2-8 | 21-61-51 | D02558B | B08 | | | D40846J | 11 | | | 001-099 |
| 2017R | 24 | GL | AZ | 0-0 | 21-61-51 | D02558B | B07 | | | D40846J | 10 | | | 001-099 |
| 2018B | 24 | GL | BA | 2-8 | 21-61-51 | D02558B | D08 | | | D40846J | 13 | | | 001-099 |
| 2018R | 24 | GL | BA | 0-0 | 21-61-51 | D02558B | D07 | | | D40846J | 12 | | | 001-099 |
| 2019B | 24 | GL | BB | 2-1 | 21-61-51 | D02558B | C01 | | | D40678J | 15 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1330

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1330 | 286N1330 | | | | E3-3 SHELF (ELECTRICAL) (continued) | | | | | | | | | | |
| 2019R | 24 | GL | BB | | 0-0 | 21-61-51 | D02558B | | C02 | | D40678J | | 14 | | 001-099 |
| 2020B | 24 | GL | BC | | 2-4 | 21-61-51 | D02558B | | A06 | | D02964B | | A06 | | 001-099 |
| 2020R | 24 | GL | BC | | 0-0 | 21-61-51 | D02558B | | A05 | | D02964B | | A05 | | 001-099 |
| 2021B | 24 | GL | BD | | 2-4 | 21-61-51 | D02558B | | A08 | | D02964B | | A08 | | 001-099 |
| 2021R | 24 | GL | BD | | 0-0 | 21-61-51 | D02558B | | A07 | | D02964B | | A07 | | 001-099 |
| 2022B | 24 | GL | BE | | 2-4 | 21-61-51 | D02558B | | C08 | | D02964B | | B08 | | 001-099 |
| 2022R | 24 | GL | BE | | 0-0 | 21-61-51 | D02558B | | C07 | | D02964B | | B07 | | 001-099 |
| 2023B | 24 | GL | BF | | 2-4 | 21-61-51 | D02558B | | A04 | | D02964B | | A04 | | 001-099 |
| 2023R | 24 | GL | BF | | 0-0 | 21-61-51 | D02558B | | A03 | | D02964B | | A03 | | 001-099 |
| 2024B | 24 | GL | BG | | 2-4 | 21-61-51 | D02558B | | A02 | | D02964B | | A02 | | 001-099 |
| 2024R | 24 | GL | BG | | 0-0 | 21-61-51 | D02558B | | A01 | | D02964B | | A01 | | 001-099 |
| 2025B | 24 | GL | BH | | 2-3 | 21-51-14 | D04130A | | B09 | | D40656J | | 47 | | 001-099 |
| 2025R | 24 | GL | BH | | 0-0 | 21-51-14 | D04130A | | A09 | | D40656J | | 46 | | 001-099 |
| 2026B | 24 | GL | BI | | 2-3 | 21-51-14 | D04130A | | B10 | | D40656J | | 49 | | 001-099 |
| 2026R | 24 | GL | BI | | 0-0 | 21-51-14 | D04130A | | A10 | | D40656J | | 48 | | 001-099 |
| 2027B | 24 | GL | BJ | | 2-3 | 21-51-14 | D04130A | | B12 | | D40656J | | 51 | | 001-099 |
| 2027R | 24 | GL | BJ | | 0-0 | 21-51-14 | D04130A | | A12 | | D40656J | | 50 | | 001-099 |
| 2029B | 24 | GL | BW | | 2-4 | 21-51-12 | D02964A | | A04 | | D40656J | | 21 | | 001-099 |
| 2029R | 24 | GL | BW | | 0-0 | 21-51-12 | D02964A | | A05 | | D40656J | | 20 | | 001-099 |
| 2030B | 24 | GL | BY | | 2-2 | 21-61-11 | D02964A | | C05 | | D40670J | | 37 | | 001-099 |
| 2030R | 24 | GL | BY | | 0-0 | 21-61-11 | D02964A | | C04 | | D40670J | | 36 | | 001-099 |
| 2031B | 24 | GL | BZ | | 2-1 | 21-51-12 | D02964B | | D01 | | D40844J | | 17 | | 001-099 |
| 2031R | 24 | GL | BZ | | 0-0 | 21-51-12 | D02964B | | D02 | | D40844J | | 18 | | 001-099 |
| 2032B | 24 | GL | CA | | 2-2 | 21-51-12 | D02964B | | D05 | | D40656J | | 15 | | 001-099 |
| 2032R | 24 | GL | CA | | 0-0 | 21-51-12 | D02964B | | D06 | | D40656J | | 16 | | 001-099 |
| 2033B | 24 | GL | DB | | 2-4 | 21-51-12 | D02964A | | B04 | | D40656J | | 14 | | 001-099 |
| 2033R | 24 | GL | DB | | 0-0 | 21-51-12 | D02964A | | B05 | | D40656J | | 13 | | 001-099 |
| 3001B | 24 | GM | AA | | 2-4 | 21-51-12 | D02964A | | C11 | | D40656J | | 23 | | 001-099 |
| 3001R | 24 | GM | AA | | 0-0 | 21-51-12 | D02964A | | C10 | | D40656J | | 22 | | 001-099 |
| 3001Y | 24 | GM | AA | | 0-0 | 21-51-12 | D02964A | | C12 | | D40656J | | 24 | | 001-099 |
| 3002B | 24 | GM | AB | | 2-4 | 21-51-12 | D02964A | | C02 | | D40656J | | 26 | | 001-099 |
| 3002R | 24 | GM | AB | | 0-0 | 21-51-12 | D02964A | | C03 | | D40656J | | 25 | | 001-099 |
| 3002Y | 24 | GM | AB | | 0-0 | 21-51-12 | D02964A | | C01 | | D40656J | | 27 | | 001-099 |
| 3003B | 24 | GM | AC | | 2-4 | 21-51-12 | D02964A | | B11 | | D40656J | | 29 | | 001-099 |
| 3003R | 24 | GM | AC | | 0-0 | 21-51-12 | D02964A | | B10 | | D40656J | | 28 | | 001-099 |
| 3003Y | 24 | GM | AC | | 0-0 | 21-51-12 | D02964A | | B12 | | D40656J | | 30 | | 001-099 |
| 3004B | 24 | GM | AD | | 2-4 | 21-51-12 | D02964A | | B02 | | D40656J | | 32 | | 001-099 |
| 3004R | 24 | GM | AD | | 0-0 | 21-51-12 | D02964A | | B03 | | D40656J | | 31 | | 001-099 |
| 3004Y | 24 | GM | AD | | 0-0 | 21-51-12 | D02964A | | B01 | | D40656J | | 33 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1330

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | |
|------------------------|-------------|----|----|-------------------------------------|-------------|---------|---------|------|------|--------|---------|------|------|-------------|--------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice |
| W1330 | 286N1330 | | | E3-3 SHELF (ELECTRICAL) (continued) | | | | | | | | | | | |
| 3005B | 24 | GM | AE | 2-4 | 21-51-12 | D02964A | | A11 | | | D40656J | 35 | | 001-099 | |
| 3005R | 24 | GM | AE | 0-0 | 21-51-12 | D02964A | | A10 | | | D40656J | 34 | | 001-099 | |
| 3005Y | 24 | GM | AE | 0-0 | 21-51-12 | D02964A | | A12 | | | D40656J | 36 | | 001-099 | |
| 3006B | 24 | GM | AF | 2-4 | 21-51-12 | D02964A | | A02 | | | D40656J | 38 | | 001-099 | |
| 3006R | 24 | GM | AF | 0-0 | 21-51-12 | D02964A | | A01 | | | D40656J | 37 | | 001-099 | |
| 3006Y | 24 | GM | AF | 0-0 | 21-51-12 | D02964A | | A03 | | | D40656J | 39 | | 001-099 | |
| 3007B | 24 | GM | AL | 2-7 | 21-61-11 | D02558A | | A02 | | | D40670J | 9 | | 001-099 | |
| 3007R | 24 | GM | AL | 0-0 | 21-61-11 | D02558A | | A01 | | | D40670J | 8 | | 001-099 | |
| 3007Y | 24 | GM | AL | 0-0 | 21-61-11 | D02558A | | A03 | | | D40670J | 10 | | 001-099 | |
| 3008B | 24 | GM | AR | 2-7 | 21-61-21 | D02558A | | B02 | | | D40670J | 24 | | 001-099 | |
| 3008R | 24 | GM | AR | 0-0 | 21-61-21 | D02558A | | B01 | | | D40670J | 23 | | 001-099 | |
| 3008Y | 24 | GM | AR | 0-0 | 21-61-21 | D02558A | | B03 | | | D40670J | 25 | | 001-099 | |
| 3009B | 24 | GM | AU | 2-8 | 21-61-31 | D02558A | | C02 | | | D40844J | 10 | | 001-099 | |
| 3009R | 24 | GM | AU | 0-0 | 21-61-31 | D02558A | | C01 | | | D40844J | 11 | | 001-099 | |
| 3009Y | 24 | GM | AU | 0-0 | 21-61-31 | D02558A | | C03 | | | D40844J | 12 | | 001-099 | |
| 3017B | 24 | GM | BK | 2-8 | 21-61-31 | D02558A | | C11 | | | D40844J | 3 | | 001-099 | |
| 3017R | 24 | GM | BK | 0-0 | 21-61-31 | D02558A | | C10 | | | D40844J | 2 | | 001-099 | |
| 3017Y | 24 | GM | BK | 0-0 | 21-61-31 | D02558A | | C12 | | | D40844J | 4 | | 001-099 | |
| 3018B | 24 | GM | BT | 2-7 | 21-61-11 | D02558A | | A11 | | | D40670J | 17 | | 001-099 | |
| 3018R | 24 | GM | BT | 0-0 | 21-61-11 | D02558A | | A10 | | | D40670J | 16 | | 001-099 | |
| 3018Y | 24 | GM | BT | 0-0 | 21-61-11 | D02558A | | A12 | | | D40670J | 18 | | 001-099 | |
| 3019B | 24 | GM | BU | 2-2 | 21-51-12 | D02964B | | A09 | | | D40656J | 19 | | 001-099 | |
| 3019R | 24 | GM | BU | 0-0 | 21-51-12 | D02964B | | A10 | | | D40656J | 17 | | 001-099 | |
| 3019Y | 24 | GM | BU | 0-0 | 21-51-12 | D02964B | | A11 | | | D40656J | 18 | | 001-099 | |
| 3020B | 24 | GM | BX | 2-7 | 21-61-21 | D02558A | | B11 | | | D40670J | 32 | | 001-099 | |
| 3020R | 24 | GM | BX | 0-0 | 21-61-21 | D02558A | | B10 | | | D40670J | 31 | | 001-099 | |
| 3020Y | 24 | GM | BX | 0-0 | 21-61-21 | D02558A | | B12 | | | D40670J | 33 | | 001-099 | |
| W1332 | 286N1332 | | | E3-2 SHELF (ELECTRICAL) | | | | | | | | | | | |
| 0346 | 22 | GA | | 3-0 | 21-51-22 | D03026C | | 2 | | | D40666J | 48 | | 001-099 | |
| 0347 | 20 | GA | | 3-0 | 21-51-22 | D03026C | | 4 | | | GD03364 | AC.. | 2 | 001-099 | |
| 0348 | 24 | GK | | 3-0 | 21-51-22 | D03026C | | 3 | | | GD03364 | ST.. | 2 | 001-099 | |
| 0350 | 24 | GK | | 3-0 | 21-51-22 | D03026B | | C13 | | | D40666J | 6 | | 001-099 | |
| 0351 | 24 | GK | | 3-0 | 21-51-22 | D03026B | | C15 | | | D40666J | 5 | | 001-099 | |
| 0352 | 24 | GK | | 3-0 | 21-51-22 | D03026B | | B13 | | | D40666J | 4 | | 001-099 | |
| 0353 | 24 | GK | | 3-0 | 21-51-22 | D03026B | | B15 | | | D40666J | 3 | | 001-099 | |
| 0354 | 24 | GK | | 3-0 | 21-51-22 | D03026B | | A13 | | | D40666J | 2 | | 001-099 | |
| 0355 | 24 | GK | | 3-0 | 21-51-22 | D03026B | | A15 | | | D40666J | 1 | | 001-099 | |
| 0356 | 24 | GK | | 3-0 | 21-51-22 | D03026B | | D07 | | | D40666J | 7 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W1330

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1332 | 286N1332 | | | | E3-2 SHELF (ELECTRICAL) (continued) | | | | | | | | | | | | |
| 0367 | 24 | | GK | | 3-0 | 21-51-22 | D03026A | | C15 | | GD03364 | DC.. | 2 | | 001-099 | | |
| 0368 | 24 | | GK | | 3-0 | 21-51-25 | D03026B | | C07 | | D40666J | 8 | | | 001-099 | | |
| 0369 | 24 | | GK | | 3-0 | 21-51-25 | D03026B | | B09 | | D40666J | 35 | | | 001-099 | | |
| 0370 | 24 | | GK | | 3-0 | 21-51-25 | D03026B | | C05 | | D40666J | 36 | | | 001-099 | | |
| 2001B | 24 | | GL | DA | 3-0 | 21-51-22 | D03026A | | B04 | | D40666J | 10 | | | 001-099 | | |
| 2001R | 24 | | GL | DA | 0-0 | 21-51-22 | D03026A | | B05 | | D40666J | 9 | | | 001-099 | | |
| 2002B | 24 | | GL | DB | 3-0 | 21-51-22 | D03026B | | D05 | | D40666J | 31 | | | 001-099 | | |
| 2002R | 24 | | GL | DB | 0-0 | 21-51-22 | D03026B | | D06 | | D40666J | 32 | | | 001-099 | | |
| 2003B | 24 | | GL | DC | 3-0 | 21-51-22 | D03026A | | A05 | | D40666J | 33 | | | 001-099 | | |
| 2003R | 24 | | GL | DC | 0-0 | 21-51-22 | D03026A | | A04 | | D40666J | 34 | | | 001-099 | | |
| 2103B | 24 | | GL | AC | 3-0 | 21-51-22 | D03026B | | B02 | | D40666J | 54 | | | 001-099 | | |
| 2103R | 24 | | GL | AC | 0-0 | 21-51-22 | D03026B | | B01 | | D40666J | 55 | | | 001-099 | | |
| 2104B | 24 | | GL | AD | 3-0 | 21-51-24 | D03026B | | C01 | | D40666J | 11 | | | 001-099 | | |
| 2104R | 24 | | GL | AD | 0-0 | 21-51-24 | D03026B | | C02 | | D40666J | 12 | | | 001-099 | | |
| 2105B | 24 | | GL | AE | 3-0 | 21-51-25 | D03026A | | D04 | | D40666J | 37 | | | 001-099 | | |
| 2105R | 24 | | GL | AE | 0-0 | 21-51-25 | D03026A | | D05 | | D40666J | 38 | | | 001-099 | | |
| 2106B | 24 | | GL | BI | 3-0 | 21-51-22 | D03026B | | D01 | | D40666J | 43 | | | 001-099 | | |
| 2106R | 24 | | GL | BI | 0-0 | 21-51-22 | D03026B | | D02 | | D40666J | 44 | | | 001-099 | | |
| 2107B | 24 | | GL | AF | 4-0 | 21-61-51 | D03026B | | A04 | | D40774J | 6 | | | 001-099 | | |
| 2107R | 24 | | GL | AF | 0-0 | 21-61-51 | D03026B | | A03 | | D40774J | 5 | | | 001-099 | | |
| 2108B | 24 | | GL | AG | 4-0 | 21-61-51 | D03026B | | A02 | | D40774J | 8 | | | 001-099 | | |
| 2108R | 24 | | GL | AG | 0-0 | 21-61-51 | D03026B | | A01 | | D40774J | 7 | | | 001-099 | | |
| 2109B | 24 | | GL | AI | 4-0 | 21-61-51 | D03026B | | A08 | | D40774J | 10 | | | 001-099 | | |
| 2109R | 24 | | GL | AI | 0-0 | 21-61-51 | D03026B | | A07 | | D40774J | 9 | | | 001-099 | | |
| 2110B | 24 | | GL | AH | 4-0 | 21-61-51 | D03026B | | B08 | | D40774J | 12 | | | 001-099 | | |
| 2110R | 24 | | GL | AH | 0-0 | 21-61-51 | D03026B | | B07 | | D40774J | 11 | | | 001-099 | | |
| 2112B | 24 | | GL | AL | 3-0 | 21-61-21 | D03026A | | C05 | | D40774J | 2 | | | 001-099 | | |
| 2112R | 24 | | GL | AL | 0-0 | 21-61-21 | D03026A | | C04 | | D40774J | 1 | | | 001-099 | | |
| 2116B | 24 | | GL | AM | 4-0 | 21-61-51 | D03026B | | A05 | | D40774J | 4 | | | 001-099 | | |
| 2116R | 24 | | GL | AM | 0-0 | 21-61-51 | D03026B | | A06 | | D40774J | 3 | | | 001-099 | | |
| 3010B | 24 | | GM | CA | 3-0 | 21-51-22 | D03026A | | C11 | | D40666J | 14 | | | 001-099 | | |
| 3010R | 24 | | GM | CA | 0-0 | 21-51-22 | D03026A | | C10 | | D40666J | 13 | | | 001-099 | | |
| 3010Y | 24 | | GM | CA | 0-0 | 21-51-22 | D03026A | | C12 | | D40666J | 15 | | | 001-099 | | |
| 3011B | 24 | | GM | CB | 3-0 | 21-51-22 | D03026A | | C02 | | D40666J | 17 | | | 001-099 | | |
| 3011R | 24 | | GM | CB | 0-0 | 21-51-22 | D03026A | | C03 | | D40666J | 16 | | | 001-099 | | |
| 3011Y | 24 | | GM | CB | 0-0 | 21-51-22 | D03026A | | C01 | | D40666J | 18 | | | 001-099 | | |
| 3012B | 24 | | GM | CC | 3-0 | 21-51-22 | D03026A | | B11 | | D40666J | 19 | | | 001-099 | | |
| 3012R | 24 | | GM | CC | 0-0 | 21-51-22 | D03026A | | B10 | | D40666J | 20 | | | 001-099 | | |
| 3012Y | 24 | | GM | CC | 0-0 | 21-51-22 | D03026A | | B12 | | D40666J | 21 | | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W1330

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1332 | 286N1332 | | | E3-2 SHELF (ELECTRICAL) (continued) | | | | | | | | | | | |
| 3013B | 24 | GM | CD | | 3-0 | 21-51-22 | D03026A | B02 | | | D40666J | 23 | | | 001-099 |
| 3013R | 24 | GM | CD | | 0-0 | 21-51-22 | D03026A | B03 | | | D40666J | 22 | | | 001-099 |
| 3013Y | 24 | GM | CD | | 0-0 | 21-51-22 | D03026A | B01 | | | D40666J | 24 | | | 001-099 |
| 3014B | 24 | GM | BJ | | 3-0 | 21-51-22 | D03026A | A11 | | | D40666J | 29 | | | 001-099 |
| 3014R | 24 | GM | BJ | | 0-0 | 21-51-22 | D03026A | A10 | | | D40666J | 28 | | | 001-099 |
| 3014Y | 24 | GM | BJ | | 0-0 | 21-51-22 | D03026A | A12 | | | D40666J | 30 | | | 001-099 |
| 3015B | 24 | GM | CE | | 3-0 | 21-51-22 | D03026A | A02 | | | D40666J | 26 | | | 001-099 |
| 3015R | 24 | GM | CE | | 0-0 | 21-51-22 | D03026A | A01 | | | D40666J | 25 | | | 001-099 |
| 3015Y | 24 | GM | CE | | 0-0 | 21-51-22 | D03026A | A03 | | | D40666J | 27 | | | 001-099 |
| 3017B | 24 | GM | CG | | 3-0 | 21-51-22 | D03026B | A11 | | | D40666J | 46 | | | 001-099 |
| 3017R | 24 | GM | CG | | 0-0 | 21-51-22 | D03026B | A10 | | | D40666J | 45 | | | 001-099 |
| 3017Y | 24 | GM | CG | | 0-0 | 21-51-22 | D03026B | A09 | | | D40666J | 47 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1330

Page 6 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|---------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE | | | | | | | | | | | |
| 0001 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | A01 | | | D00753 | 1 | VP | | 001-099 |
| 0001 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | A01 | | | D00753 | 1 | | | 115-199 |
| 0002 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | B01 | | | D00753 | 2 | | | 001, 004-099 |
| 0002 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | B01 | | | D00753 | 2 | VP | | 002-003, 115-199 |
| 0003 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | C01 | | | D00753 | 3 | VP | | 001-004, 006, 009-099 |
| 0003 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | C01 | | | D00753 | 3 | | | 005, 007-008, 115-199 |
| 0004 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | D01 | | | D00753 | 4 | VP | | 001-004, 006, 009-099, 115-199 |
| 0004 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | D01 | | | D00753 | 4 | | | 005, 007-008 |
| 0005 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | E01 | | | D00753 | 5 | VP | | 001, 009 |
| 0005 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | E01 | | | D00753 | 5 | | | 002-008, 010-099, 115-199 |
| 0006 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | F01 | | | D00753 | 6 | VP | | 001, 005, 007-009, 115-199 |
| 0006 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | F01 | | | D00753 | 6 | | | 002-004, 006, 010-099 |
| 0007 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | G01 | | | D00753 | 7 | VP | | 001-099 |
| 0007 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | G01 | | | D00753 | 7 | | | 115-199 |
| 0008 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | H01 | | | D00753 | 8 | VP | | 001, 004-099, 115-199 |
| 0008 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | H01 | | | D00753 | 8 | | | 002-003 |
| 0009 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | J01 | | | D00753 | 9 | VP | | 001-003, 005, 007-009, 115-199 |
| 0009 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | J01 | | | D00753 | 9 | | | 004, 006, 010-099 |
| 0010 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | K01 | | | D00753 | 10 | VP | | ALL |
| 0011 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | A02 | | | D00753 | 11 | VP | | 001-003, 005, 007-009 |
| 0011 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | A02 | | | D00753 | 11 | | | 004, 006, 010-099, 115-199 |
| 0012 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | B02 | | | D00753 | 12 | VP | | 001-099 |
| 0012 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | B02 | | | D00753 | 12 | | | 115-199 |
| 0013 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | C02 | | | D00753 | 13 | VP | | ALL |
| 0014 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | D02 | | | D00753 | 14 | | | 001, 009, 115-199 |
| 0014 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | D02 | | | D00753 | 14 | VP | | 002-008, 010-099 |
| 0015 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | E02 | | | D00753 | 15 | VP | | ALL |
| 0016 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | F02 | | | D00753 | 16 | VP | | 001-008, 010-099, 115-199 |
| 0016 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | F02 | | | D00753 | 16 | | | 009 |
| 0017 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | G02 | | | D00753 | 17 | | | 001 |
| 0017 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | G02 | | | D00753 | 17 | VP | | 002-099, 115-199 |
| 0018 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | H02 | | | D00753 | 18 | | | 001, 004, 006, 010-099, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0018 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | H02 | | | D00753 | 18 | VP | | 002-003, 005, 007-009 |
| 0019 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | J02 | | | D00753 | 19 | | | 001-003, 005, 007-099, 115-199 |
| 0019 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | J02 | | | D00753 | 19 | VP | | 004, 006 |
| 001CO | | | | AF | 0-0 | 34-53-21 | D00253B | =C71 | | | D41755J | =C1 | | | ALL |
| 001CX | | | JB | AF | 1-11 | 34-53-21 | D00253B | 71 | | | D41755J | =A1 | | | 001-099 |
| 001CX | | | JB | AF | 1-10 | 34-53-21 | D00253B | 71 | | | D41755J | =A1 | | | 115-199 |
| 0020 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | K02 | | | D00753 | 20 | | | 001, 003, 005, 009 |
| 0020 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | K02 | | | D00753 | 20 | VP | | 002, 004, 006-008, 010-099, 115-199 |
| 0021 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | A03 | | | D00753 | 21 | VP | | 001-002, 004-005, 009 |
| 0021 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | A03 | | | D00753 | 21 | | | 003, 006-008, 010-099, 115-199 |
| 0022 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | B03 | | | D00753 | 22 | VP | | 001-002, 005-006, 009-099 |
| 0022 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | B03 | | | D00753 | 22 | | | 003-004, 007-008, 115-199 |
| 0023 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | C03 | | | D00753 | 23 | VP | | 001, 003, 006-007, 010-099 |
| 0023 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | C03 | | | D00753 | 23 | | | 002, 004-005, 008-009, 115-199 |
| 0024 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | D03 | | | D00753 | 24 | VP | | 001-002, 005-006, 008, 010, 115-199 |
| 0024 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | D03 | | | D00753 | 24 | | | 003-004, 007, 009, 011-099 |
| 0025 | 24 | | GK | | 3-0 | 34-53-22 | D00253B | E03 | | | D00753 | 25 | | | ALL |
| 0026 | 24 | | GK | | 2-4 | 34-53-21 | D00253B | H03 | | | D41527J | 9 | | | 001-002 |
| 0026 | 24 | | GK | | 3-0 | 34-53-21 | D00253B | H03 | | | D41527J | 9 | | | 115-199 |
| 0027 | 24 | | GK | | 3-3 | 34-53-22 | D00253B | J05 | | | TB0137Y | A091 | BJ | | 001-099 |
| 0027 | 24 | | GK | | 3-0 | 34-53-22 | D00753 | 29 | | | D00253B | J05 | | | 115-199 |
| 0028 | 24 | | GK | | 2-4 | 34-53-21 | D00253B | K03 | | | D41527J | 20 | | | 001-099 |
| 0028 | 24 | | GK | | 3-0 | 34-53-21 | D00253B | K03 | | | D41527J | 2 | | | 115-199 |
| 0029 | 22 | | GA | | 2-9 | 34-53-21 | D00253B | E06 | | | D42091J | 7 | | | 001-099 |
| 0029 | 22 | | GA | | 3-0 | 34-53-21 | D42091J | 7 | | | D00253B | E06 | | | 115-199 |
| 002CO | | | | AG | 0-0 | 34-53-21 | D00253C | =C12 | | | D01679 | =C1 | | | ALL |
| 002CX | | 66 | | AG | 1-0 | 34-53-21 | D00253C | 12 | | | D01679 | =A1 | | | 001-099 |
| 002CX | | 66 | | AG | 0-11 | 34-53-21 | D00253C | 12 | | | D01679 | =A1 | | | 115-199 |
| 0030 | 24 | | GK | | 4-0 | 31-31-61 | D00301B | E02 | | | D41355J | 49 | | | 001-099 |
| 0031 | 20 | | GA | | 1-6 | 34-53-21 | D41527J | | | AA | GD01935 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 2

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W1420
Page 3
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0052 | 22 | | GA | | 3-0 | 34-55-21 | D00243B | D05 | | | D42039J | 1 | | | 115-199 |
| 0053 | 22 | | GA | | 2-7 | 34-55-21 | D00243B | E05 | | | GD01933 | DC.. | 2 | | 001-099 |
| 0053 | 22 | | GA | | 2-0 | 34-55-21 | D00243B | E05 | | | D42091J | 25 | | | 115-199 |
| 0054 | 24 | | GK | | 3-4 | 34-53-22 | D00253A | C05 | | | TB0137Y | A091 | BJ | | 001-099 |
| 0054 | 24 | | GK | | 3-0 | 34-53-22 | D00253A | C05 | | | D00753 | 27 | | | 115-199 |
| 0055 | 24 | | GK | | 3-4 | 34-53-22 | D00253A | D05 | | | TB0137Y | A091 | BJ | | 001-099 |
| 0055 | 24 | | GK | | 3-0 | 34-53-22 | D00253A | D05 | | | D00753 | 28 | | | 115-199 |
| 0056 | 20 | | GA | | 1-6 | 34-55-21 | D42091J | | | AF | GD01934 | ST.. | 2 | | ALL |
| 0057 | 20 | | GA | | 1-6 | 34-55-21 | D41355J | | | AG | GD01934 | ST.. | 2 | | ALL |
| 0058 | 20 | | GA | | 1-6 | 34-61-13 | D41355J | | | AH | GD01934 | ST.. | 2 | | ALL |
| 0059 | 20 | | GA | | 1-6 | 34-22-29 | D41355J | | | AI | GD01934 | ST.. | 2 | | ALL |
| 005CO | | | | MC | 0-0 | 34-45-02 | D01683 | = C1 | | | D41203J | = C1 | | | ALL |
| 005CX | | 66 | | MC | 1-8 | 34-45-02 | D01683 | = A1 | | | D41203J | = A1 | | | 001-099 |
| 005CX | | 66 | | MC | 2-1 | 34-45-02 | D01683 | = A1 | | | D41203J | = A1 | | | 115-199 |
| 0061 | 20 | | GA | | 1-6 | 22-41-11 | D41303J | | | AJ | GD01933 | ST.. | 2 | | ALL |
| 0062 | 20 | | GA | | 1-6 | 22-41-11 | D41355J | | | AK | GD01933 | ST.. | 2 | | ALL |
| 0063 | 20 | | GA | | 1-6 | 22-41-11 | D41401J | | | AL | GD01931 | ST.. | 2 | | ALL |
| 0064 | 20 | | GA | | 1-6 | 22-41-11 | D41303J | | | AM | GD01933 | ST.. | 2 | | ALL |
| 0065 | 20 | | GA | | 1-6 | 22-41-11 | D41303J | | | AN | GD01933 | ST.. | 2 | | ALL |
| 0066 | 20 | | GA | | 1-6 | 22-41-11 | D41355J | | | AP | GD01933 | ST.. | 2 | | ALL |
| 0067 | 20 | | GA | | 1-6 | 22-41-12 | D41303J | | | AQ | GD01933 | ST.. | 2 | | ALL |
| 0068 | 20 | | GA | | 1-6 | 22-41-12 | D41303J | | | AR | GD01933 | ST.. | 2 | | ALL |
| 0070 | 22 | | GA | | 2-9 | 22-41-11 | D00079A | E14 | | | D41303J | 7 | | | 001-099 |
| 0070 | 22 | | GA | | 3-0 | 22-41-11 | D00079A | E14 | | | D41303J | 7 | | | 115-199 |
| 0071 | 22 | | GA | | 2-9 | 22-41-11 | D00079A | C11 | | | D41303J | 14 | | | 001-099 |
| 0071 | 22 | | GA | | 3-0 | 22-41-11 | D00079A | C11 | | | D41303J | 14 | | | 115-199 |
| 0072 | 22 | | GA | | 2-9 | 22-14-31 | D00079A | D04 | | | D41303J | 4 | | | 001-099 |
| 0073 | 22 | | GA | | 2-8 | 22-14-31 | D00079A | H04 | | | D41355J | 37 | | | 001-099 |
| 0074 | 22 | | GA | | 2-9 | 22-41-11 | D00079A | C09 | | | D41303J | 5 | | | 001-099 |
| 0074 | 22 | | GA | | 3-0 | 22-41-11 | D00079A | C09 | | | D41303J | 5 | | | 115-199 |
| 0075 | 22 | | GA | | 2-9 | 22-41-11 | D00079A | C10 | | | D41303J | 6 | | | 001-099 |
| 0075 | 22 | | GA | | 3-0 | 22-41-11 | D00079A | C10 | | | D41303J | 6 | | | 115-199 |
| 0076 | 22 | | GA | | 2-2 | 22-41-13 | D00079A | K11 | | | D41741J | 4 | | | 001-099 |
| 0076 | 22 | | GA | | 2-0 | 22-41-13 | D00079A | K11 | | | D41741J | 4 | | | 115-199 |
| 0077 | 22 | | GA | | 2-2 | 22-41-13 | D00079A | K14 | | | D41741J | 5 | | | 001-099 |
| 0077 | 22 | | GA | | 2-0 | 22-41-13 | D00079A | K14 | | | D41741J | 5 | | | 115-199 |
| 0078 | 22 | | GA | | 2-2 | 22-41-13 | D00079A | J14 | | | D41741J | 6 | | | 001-099 |
| 0078 | 22 | | GA | | 2-0 | 22-41-13 | D00079A | J14 | | | D41741J | 6 | | | 115-199 |
| 0079 | 22 | | GA | | 2-2 | 22-41-13 | D00079A | K13 | | | D41741J | 7 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0079 | 22 | | GA | | 2-0 | 22-41-13 | D00079A | | K13 | | D41741J | | 7 | | 115-199 |
| 0080 | 22 | | GA | | 2-2 | 22-41-13 | D00079A | | J13 | | D41741J | | 8 | | 001-099 |
| 0080 | 22 | | GA | | 2-0 | 22-41-13 | D00079A | | J13 | | D41741J | | 8 | | 115-199 |
| 0081 | 22 | | GA | | 2-2 | 22-41-13 | D00079A | | J12 | | D41741J | | 9 | | 001-099 |
| 0081 | 22 | | GA | | 2-0 | 22-41-13 | D00079A | | J12 | | D41741J | | 9 | | 115-199 |
| 0082 | 22 | | GA | | 2-2 | 22-41-13 | D00079A | | K12 | | D41741J | | 10 | | 001-099 |
| 0082 | 22 | | GA | | 2-0 | 22-41-13 | D00079A | | K12 | | D41741J | | 10 | | 115-199 |
| 0083 | 20 | | GA | | 2-3 | 22-41-13 | D41741J | | 14 | | GD01931 | DC.. | 2 | | 001-099 |
| 0083 | 20 | | GA | | 3-0 | 22-41-13 | D41741J | | 14 | | GD01931 | DC.. | 2 | | 115-199 |
| 0084 | 20 | | GA | | 2-7 | 22-41-11 | D41303J | | 47 | | D00079C | | 3 | | 001-099 |
| 0084 | 20 | | GA | | 3-0 | 22-41-11 | D41303J | | 47 | | D00079C | | 3 | | 115-199 |
| 0085 | 20 | | GA | | 2-0 | 22-41-11 | D00079C | | 2 | | GD01931 | AC.. | 2 | | 001-099 |
| 0085 | 20 | | GA | | 3-0 | 22-41-11 | D00079C | | 2 | | GD01931 | AC.. | 2 | | 115-199 |
| 0086 | 20 | | GA | | 2-0 | 22-41-11 | D00079C | | 5 | | GD01931 | ST.. | 2 | | 001-099 |
| 0086 | 20 | | GA | | 3-0 | 22-41-11 | D00079C | | 5 | | GD01931 | ST.. | 2 | | 115-199 |
| 0087 | 20 | | GA | | 2-0 | 22-41-11 | D00079C | | 7 | | GD01931 | DC.. | 2 | | 001-099 |
| 0087 | 20 | | GA | | 3-0 | 22-41-11 | D00079C | | 7 | | GD01931 | DC.. | 2 | | 115-199 |
| 0088 | 20 | | GA | | 2-0 | 22-41-11 | D00079C | | 11 | | GD01931 | DC.. | 2 | | 001-099 |
| 0088 | 20 | | GA | | 3-0 | 22-41-11 | D00079C | | 11 | | GD01931 | DC.. | 2 | | 115-199 |
| 0090 | 22 | | GA | | 0-7 | 22-41-11 | D00079A | | B06 | | D00079A | | B14 | | 001-099 |
| 0091 | 22 | | GA | | 2-0 | 32-61-12 | D41355J | | 36 | | D42091J | | 2 | | 001-099 |
| 0091 | 22 | | GA | | 2-0 | 32-61-12 | D42091J | | 2 | | D41355J | | 36 | | 115-199 |
| 0094 | 22 | | GA | | 2-0 | 32-61-12 | D41355J | | 39 | | D42091J | | 3 | | 001-099 |
| 0094 | 22 | | GA | | 2-0 | 32-61-12 | D42091J | | 3 | | D41355J | | 39 | | 115-199 |
| 0095 | 22 | | GA | | 0-7 | 22-41-11 | D00079A | | C13 | | D00079A | | E06 | | 001-099 |
| 0095 | 22 | | GA | | 2-0 | 22-41-11 | D00079A | | C13 | | D00079A | | E06 | | 115-199 |
| 0096 | 24 | | GK | | 2-0 | 32-61-12 | D41355J | | 23 | | D42091J | | 1 | | 001-099 |
| 0096 | 22 | | GA | | 2-0 | 32-61-12 | D42091J | | 1 | | D41355J | | 23 | | 115-199 |
| 0097 | 24 | | GK | | 2-0 | 32-61-12 | D41355J | | 38 | | D42091J | | 27 | | 001-099 |
| 0097 | 24 | | GK | | 2-0 | 32-61-12 | D42091J | | 27 | | D41355J | | 38 | | 115-199 |
| 0098 | 22 | | GA | | 0-7 | 22-41-11 | D00079A | | H14 | | D00079A | | K06 | | 001-099 |
| 0098 | 22 | | GA | | 2-0 | 22-41-11 | D00079A | | H14 | | D00079A | | K06 | | 115-199 |
| 0099 | 22 | | GA | | 0-7 | 22-41-11 | D00079A | | F06 | | D00079A | | H15 | | 115-199 |
| 0107 | 24 | | GK | | 2-5 | 34-53-21 | D41527J | | 7 | | D00253A | | G07 | | 001-099 |
| 0108 | 20 | | GA | | 2-7 | 34-53-21 | D00253C | | 8 | | GD01935 | DC.. | 2 | | 001-099 |
| 0111 | 24 | | GK | | 2-5 | 34-53-21 | D41527J | | 11 | | D00253A | | K05 | | 001-099 |
| 0112 | 24 | | GK | | 2-5 | 34-53-21 | D41527J | | 12 | | D00253A | | B03 | | 001-099 |
| 0113 | 24 | | GK | | 3-0 | 34-53-21 | D41527J | | 13 | | D41355J | | 22 | | 115-199 |
| 0115 | 24 | | GK | | 2-5 | 34-53-21 | D41527J | | 15 | | D00253A | | J05 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | | | |
| 0117 | 24 | | GK | | 2-4 | 34-53-21 | D41527J | 17 | | | | D00253B | G05 | | | 001-002 |
| 0119 | 24 | | GK | | 2-4 | 34-53-21 | D00253B | J03 | | | | D41527J | 19 | | | 001-002 |
| 0126 | 20 | | GA | | 3-5 | 34-51-11 | D00231C | 3 | | | | GD01932 | AC.. | 2 | | 001-099 |
| 0127 | 20 | | GA | | 4-2 | 34-51-11 | D00231C | 4 | | | | GD01934 | ST.. | 2 | | 001-099 |
| 0128 | 22 | | GA | | 2-3 | 34-51-11 | D43001J | 4 | | | | D00231B | A11 | | | 001-099 |
| 0129 | 22 | | GA | | 1-10 | 34-51-11 | SM00002 | | | WI | | D00231B | A15 | | | 001-099 |
| 012CO | | | | DF | 0-0 | 34-51-11 | D00231C | = C1 | | | | D42149J | = C1 | | | 001-099 |
| 012CX | | 66 | | DF | 1-0 | 34-51-11 | D00231C | 1 | | | | D42149J | = A1 | | | 001-099 |
| 0130 | 22 | | GA | | 2-1 | 34-51-11 | D43001J | 11 | | | | SM00002 | | WI | | 001-099 |
| 0131 | 20 | | GA | | 4-4 | 34-51-11 | D43001J | | | | BK | GD01934 | ST.. | 2 | | 001-099 |
| 0132 | 20 | | GA | | 4-1 | 34-51-11 | D43009J | | | | BL | GD01934 | ST.. | 2 | | 001-099 |
| 0133 | 20 | | GA | | 4-4 | 34-51-11 | D43001J | | | | BM | GD01934 | ST.. | 2 | | 001-099 |
| 0134 | 20 | | GA | | 3-7 | 34-22-19 | D43001J | | | | BN | GD01932 | ST.. | 2 | | 001-099 |
| 0135 | 22 | | GA | | 2-5 | 23-51-12 | D41303J | 50 | | | | GD01935 | ST.. | 2 | | 001-099 |
| 0136 | 22 | | GA | | 2-5 | 23-51-12 | D41303J | 53 | | | | GD01935 | ST.. | 2 | | 001-099 |
| 0137 | 22 | | GA | | 1-8 | 34-32-11 | D43009J | 6 | | | | D00231B | A02 | | | 001-099 |
| 0138 | 22 | | GA | | 1-8 | 34-32-11 | D43009J | 7 | | | | D00231B | B02 | | | 001-099 |
| 0139 | 22 | | GA | | 1-8 | 34-32-11 | D43009J | 8 | | | | D00231B | C02 | | | 001-099 |
| 013CO | | | | DG | 0-0 | 34-32-11 | D00231C | = C5 | | | | D41749J | = C1 | | | 001-099 |
| 013CX | | 66 | | DG | 0-10 | 34-32-11 | D00231C | 5 | | | | D41749J | = A1 | | | 001-099 |
| 0142 | 24 | | GK | | 3-0 | 34-53-21 | D00253A | G07 | | | | D41527J | 12 | | | 115-199 |
| 0143 | 24 | | GK | | 3-0 | 34-53-21 | D00253A | J05 | | | | D41527J | 3 | | | 115-199 |
| 0145 | 20 | | GA | | 2-3 | 34-53-21 | D41527J | 13 | | | | GD01935 | DC.. | 2 | | 001-099 |
| 0145 | 22 | | GA | | 2-0 | 34-53-21 | D41527J | 6 | | | | GD01935 | ST.. | 2 | | 115-199 |
| 014CO | | | | MB | 0-0 | 34-53-21 | D00253A | = C71 | | | | D41801J | = C1 | | | 001-099 |
| 014CO | | | | DZ | 0-0 | 34-53-21 | D00253A | = C71 | | | | D41801J | = C1 | | | 115-199 |
| 014CX | | | JB | MB | 2-0 | 34-53-21 | D00253A | 71 | | | | D41801J | = A1 | | | 001-099 |
| 014CX | | | JB | DZ | 1-10 | 34-53-21 | D00253A | 71 | | | | D41801J | = A1 | | | 115-199 |
| 0201 | 20 | | GA | | 4-2 | 23-11-21 | D00301C | 2 | | | | D40700J | 5 | | | 001-099 |
| 0202 | 20 | | GA | | 4-2 | 23-11-21 | D00301C | 3 | | | | D40700J | 6 | | | 001-099 |
| 0203 | 20 | | GA | | 4-2 | 23-11-21 | D00301C | 7 | | | | D40700J | 7 | | | 001-099 |
| 0204 | 20 | | GA | | 3-6 | 23-11-21 | D00301C | 8 | | | | GD01930 | AC.. | 2 | | 001-099 |
| 0205 | 20 | | GA | | 3-6 | 23-11-21 | D00301C | 10 | | | | GD01931 | ST.. | 2 | | 001-099 |
| 0206 | 20 | | GA | | 3-7 | 23-11-21 | D42045J | | | | CA | GD01931 | ST.. | 2 | | 001-099 |
| 0207 | 22 | | GA | | 4-0 | 23-51-14 | D00301B | B02 | | | | D41355J | 34 | | | 001-099 |
| 0208 | 22 | | GA | | 1-11 | 23-11-21 | D42045J | 5 | | | | D00301B | D05 | | | 001-099 |
| 0209 | 22 | | GA | | 1-11 | 23-11-21 | D42045J | 3 | | | | D00301B | F05 | | | 001-099 |
| 0210 | 22 | | GA | | 1-11 | 23-11-21 | D42045J | 4 | | | | D00301B | E05 | | | 001-099 |
| 0211 | 22 | | GA | | 1-11 | 23-11-21 | D42045J | 6 | | | | D00301B | D02 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------------------|----------|---------|------|-------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | |
| 0212 | 22 | | GA | | 2-1 | 23-11-21 | D42045J | | 7 | | D42059J | | 7 | | 001-099 |
| 0213 | 22 | | GA | | 2-1 | 23-11-21 | D42045J | | 8 | | D42059J | | 8 | | 001-099 |
| 0214 | 20 | | GA | | 1-7 | 23-11-21 | D00301C | | 1 | | D42059J | | 3 | | 001-099 |
| 0215 | 20 | | GA | | 1-7 | 23-11-21 | D00301C | | 9 | | D42059J | | 6 | | 001-099 |
| 0216 | 22 | | GA | | 1-7 | 23-11-21 | D00301B | | B05 | | D42059J | | 1 | | 001-099 |
| 0217 | 22 | | GA | | 1-7 | 23-11-21 | D00301B | | C05 | | D42059J | | 2 | | 001-099 |
| 0218 | 22 | | GA | | 1-7 | 23-11-21 | D00301B | | H05 | | D42059J | | 4 | | 001-099 |
| 0219 | 22 | | GA | | 2-9 | 23-11-21 | D00301B | | C01 | | SM00003 | | | WI | 001-099 |
| 021CO | | | | DB | 0-0 | 23-11-21 | D00301B | | = C71 | | D42057J | | = C1 | | 001-099 |
| 021CX | | 65 | | DB | 1-0 | 23-11-21 | D00301B | | 71 | | D42057J | | = A1 | | 001-099 |
| 0220 | 20 | | GA | | 2-11 | 23-11-21 | D42059J | | 5 | | SM00003 | | | WI | 001-099 |
| 0221 | 24 | | GK | | 2-0 | 23-51-14 | SM00003 | | | WI | D41355J | | 24 | | 001-099 |
| 0225 | 22 | | GA | | 2-3 | 34-51-21 | D43015J | | 5 | | D00235C | | 2 | | 001-099 |
| 0226 | 20 | | GA | | 3-10 | 34-51-21 | GD01930 | | AC.. | 2 | D00235C | | 3 | | 001-099 |
| 0227 | 20 | | GA | | 4-0 | 34-51-21 | GD01932 | | ST.. | 2 | D00235C | | 4 | | 001-099 |
| 0228 | 22 | | GA | | 1-11 | 34-51-21 | D43005J | | 1 | | D00235B | | A11 | | 001-099 |
| 0229 | 22 | | GA | | 2-8 | 34-51-21 | D00235B | | A15 | | SM00040 | | | WI | 001-099 |
| 022CO | | | | DA | 0-0 | 34-51-21 | D00235C | | = C1 | | D42151J | | = C1 | | 001-099 |
| 022CX | | 66 | | DA | 1-0 | 34-51-21 | D00235C | | 1 | | D42151J | | = A1 | | 001-099 |
| 0230 | 22 | | GA | | 2-11 | 34-51-21 | D43005J | | 8 | | SM00040 | | | WI | 001-099 |
| 0231 | 20 | | GA | | 4-3 | 34-51-21 | D43005J | | | CK | GD01931 | | ST.. | 2 | 001-099 |
| 0232 | 20 | | GA | | 2-8 | 34-51-21 | D42091J | | | CL | GD01932 | | ST.. | 2 | 001-099 |
| 0233 | 20 | | GA | | 4-3 | 34-51-21 | D43005J | | | CM | GD01931 | | ST.. | 2 | 001-099 |
| 0234 | 20 | | GA | | 4-5 | 34-22-29 | D43005J | | | CN | GD01932 | | ST.. | 2 | 001-099 |
| 0235 | 22 | | GA | | 2-4 | 23-51-12 | D41355J | | 52 | | GD01935 | | ST.. | 2 | 001-099 |
| 0236 | 22 | | GA | | 4-0 | 34-51-21 | D00235B | | D02 | | GD01931 | | ST.. | 2 | 001-099 |
| 0239 | 22 | | GA | | 2-6 | 34-57-11 | D45001J | | 1 | | SM00002 | | | WI | 001-099 |
| 0240 | 22 | | GA | | 3-5 | 34-57-21 | D45005J | | 1 | | SM00040 | | | WI | 001-099 |
| 0242 | 22 | | GA | | 5-2 | 34-45-02 | D43005J | | | DV | GD01934 | | ST.. | 2 | 001-099 |
| 0242 | 22 | | GA | | 5-0 | 34-45-02 | D43005J | | | DV | GD01934 | | ST.. | 2 | 115-199 |
| 0243 | 22 | | GA | | 5-2 | 34-45-02 | D43005J | | | DW | GD01934 | | ST.. | 2 | 001-099 |
| 0243 | 22 | | GA | | 5-0 | 34-45-02 | D43005J | | | DW | GD01934 | | ST.. | 2 | 115-199 |
| 0380 | 20 | | GA | | 2-0 | 34-53-21 | D00253C | | 8 | | GD01935 | | DC.. | 2 | 115-199 |
| 1001 | 22 | | GT | BD | 3-0 | 22-14-31 | D00079A | | D04 | | D41303J | | 4 | | 115-199 |
| 1001Z | | | | BD | 0-0 | 22-14-31 | D00079A | | DED | | D41303J | | DED | | 115-199 |
| 1002 | 22 | | GT | BE | 3-0 | 22-14-31 | D00079A | | H04 | | D41355J | | 37 | | 115-199 |
| 1002Z | | | | BE | 0-0 | 22-14-31 | D00079A | | DED | | D41355J | | DED | | 115-199 |
| 1101 | 22 | | GA | | 2-6 | 34-51-11 | D43011J | | 1 | | D00231C | | 2 | | 001-099 |
| 2001B | 24 | | GL | AH | 2-0 | 23-51-12 | D41355J | | 14 | | D42091J | | 23 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 2001B | 24 | GL | AH | | 2-0 | 23-51-12 | D41355J | | 14 | | D42091J | 36 | | | 115-199 |
| 2001R | 24 | GL | AH | | 0-0 | 23-51-12 | D41355J | | 13 | | D42091J | 22 | | | 001-099 |
| 2001R | 24 | GL | AH | | 0-0 | 23-51-12 | D41355J | | 13 | | D42091J | 35 | | | 115-199 |
| 2102B | 22 | GB | BH | | 1-8 | 34-51-11 | D43009J | | 5 | | D00231B | D15 | | | 001-099 |
| 2102R | 22 | GB | BH | | 0-0 | 34-51-11 | D43009J | | 4 | | D00231B | C15 | | | 001-099 |
| 2103B | 24 | GL | CD | | 3-8 | 23-51-12 | D41303J | | 49 | | D00231B | C07 | | | 001-099 |
| 2103R | 24 | GL | CD | | 0-0 | 23-51-12 | D41303J | | 48 | | D00231B | B07 | | | 001-099 |
| 2104B | 24 | GL | CE | | 3-8 | 23-51-12 | D41303J | | 52 | | D00231B | D04 | | | 001-099 |
| 2104R | 24 | GL | CE | | 0-0 | 23-51-12 | D41303J | | 51 | | D00231B | C04 | | | 001-099 |
| 2201B | 24 | GL | CH | | 4-0 | 23-21-11 | D00301B | D03 | | | D41355J | 26 | | | 001-099 |
| 2201R | 24 | GL | CH | | 0-0 | 23-21-11 | D00301B | C03 | | | D41355J | 25 | | | 001-099 |
| 2202B | 22 | GB | BQ | | 4-7 | 34-51-21 | D42091J | | 28 | | D00235B | D15 | | | 001-099 |
| 2202R | 22 | GB | BQ | | 0-0 | 34-51-21 | D42091J | | 26 | | D00235B | C15 | | | 001-099 |
| 2203B | 24 | GL | CF | | 4-6 | 23-51-12 | D41355J | | 51 | | D00235B | C07 | | | 001-099 |
| 2203R | 24 | GL | CF | | 0-0 | 23-51-12 | D41355J | | 50 | | D00235B | B07 | | | 001-099 |
| 2701B | 24 | G2 | CA | | 1-11 | 23-11-21 | D42045J | | 10 | | D00301B | H03 | | | 001-099 |
| 2701R | 24 | G2 | CA | | 0-0 | 23-11-21 | D42045J | | 9 | | D00301B | G03 | | | 001-099 |
| 2701Z | | | CA | | 0-0 | 23-11-21 | D42045J | | | CA | D00301B | DED | | | 001-099 |
| 2702B | 24 | G2 | CB | | 4-0 | 23-51-14 | D00301B | B01 | | | D41355J | 41 | | | 001-099 |
| 2702R | 24 | G2 | CB | | 0-0 | 23-51-14 | D00301B | A01 | | | D41355J | 40 | | | 001-099 |
| 2702Z | | | CB | | 0-0 | 23-51-14 | D00301B | DED | | | D41355J | 42 | | | 001-099 |
| 2703B | 24 | G2 | CC | | 4-0 | 23-51-14 | D00301B | E01 | | | D41355J | 44 | | | 001-099 |
| 2703R | 24 | G2 | CC | | 0-0 | 23-51-14 | D00301B | D01 | | | D41355J | 43 | | | 001-099 |
| 2703Z | | | CC | | 0-0 | 23-51-14 | D00301B | DED | | | D41355J | 45 | | | 001-099 |
| 5001B | 24 | G2 | AA | | 2-5 | 34-53-21 | D41527J | | 23 | | D00253A | F07 | | | 001-099 |
| 5001B | 24 | G2 | AA | | 3-0 | 34-53-21 | D41527J | | 11 | | D00253A | F07 | | | 115-199 |
| 5001R | 24 | G2 | AA | | 0-0 | 34-53-21 | D41527J | | 22 | | D00253A | E07 | | | 001-099 |
| 5001R | 24 | G2 | AA | | 0-0 | 34-53-21 | D41527J | | 10 | | D00253A | E07 | | | 115-199 |
| 5001Z | | | AA | | 0-0 | 34-53-21 | D41527J | | | AA | D00253A | DED | | | ALL |
| 5002B | 24 | G2 | AB | | 2-8 | 34-53-21 | D41303J | | 2 | | D00253B | B05 | | | 001-099 |
| 5002B | 24 | G2 | AB | | 3-0 | 34-53-21 | D41303J | | 2 | | D00253B | B05 | | | 115-199 |
| 5002R | 24 | G2 | AB | | 0-0 | 34-53-21 | D41303J | | 1 | | D00253B | A05 | | | ALL |
| 5002Z | | | AB | | 0-0 | 34-53-21 | D41303J | | | AB | D00253B | DED | | | ALL |
| 5003B | 24 | G2 | AC | | 2-8 | 34-53-21 | D41355J | | 11 | | D00253A | J07 | | | 001-099 |
| 5003B | 24 | G2 | AC | | 3-0 | 34-53-21 | D41355J | | 11 | | D00253A | J07 | | | 115-199 |
| 5003R | 24 | G2 | AC | | 0-0 | 34-53-21 | D41355J | | 10 | | D00253A | H07 | | | ALL |
| 5003Z | | | AC | | 0-0 | 34-53-21 | D41355J | | | AC | D00253A | DED | | | ALL |
| 5006B | 24 | G2 | AL | | 2-3 | 34-55-21 | D42091J | | 19 | | D00243B | E03 | | | 001-099 |
| 5006B | 24 | G2 | AL | | 2-0 | 34-55-21 | D42091J | | 19 | | D00243B | E03 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5006R | 24 | G2 | AL | | 0-0 | 34-55-21 | D42091J | 18 | | | D00243B | D03 | | | ALL |
| 5006Z | | | AL | | 0-0 | 34-55-21 | D42091J | | | AF | D00243B | DED | | | ALL |
| 5007B | 24 | G2 | AM | | 2-1 | 34-55-21 | D41355J | 28 | | | D00243B | B03 | | | 001-099 |
| 5007B | 24 | G2 | AM | | 2-0 | 34-55-21 | D41355J | 28 | | | D00243B | B03 | | | 115-199 |
| 5007R | 24 | G2 | AM | | 0-0 | 34-55-21 | D41355J | 27 | | | D00243B | A03 | | | ALL |
| 5007Z | | | AM | | 0-0 | 34-55-21 | D41355J | | | AG | D00243B | DED | | | ALL |
| 5008B | 24 | G2 | AN | | 2-1 | 34-61-13 | D41355J | 5 | | | D00243B | H01 | | | 001-099 |
| 5008B | 24 | G2 | AN | | 2-0 | 34-61-13 | D41355J | 5 | | | D00243B | H01 | | | 115-199 |
| 5008R | 24 | G2 | AN | | 0-0 | 34-61-13 | D41355J | 4 | | | D00243B | G01 | | | ALL |
| 5008Z | | | AN | | 0-0 | 34-61-13 | D41355J | | | AH | D00243B | DED | | | ALL |
| 5009B | 24 | G2 | AP | | 2-1 | 34-22-29 | D41355J | 8 | | | D00243B | H03 | | | 001-099 |
| 5009B | 24 | G2 | AP | | 2-0 | 34-22-29 | D41355J | 8 | | | D00243B | H03 | | | 115-199 |
| 5009R | 24 | G2 | AP | | 0-0 | 34-22-29 | D41355J | 7 | | | D00243B | G03 | | | ALL |
| 5009Z | | | AP | | 0-0 | 34-22-29 | D41355J | | | AI | D00243B | DED | | | ALL |
| 5011B | 24 | G2 | AQ | | 2-9 | 22-41-11 | D41303J | 12 | | | D00079A | B15 | | | 001-099 |
| 5011B | 24 | G2 | AQ | | 3-0 | 22-41-11 | D41303J | 12 | | | D00079A | B15 | | | 115-199 |
| 5011R | 24 | G2 | AQ | | 0-0 | 22-41-11 | D41303J | 11 | | | D00079A | A15 | | | ALL |
| 5011Z | | | AQ | | 0-0 | 22-41-11 | D41303J | | | AJ | D00079A | DED | | | ALL |
| 5012B | 24 | G2 | AR | | 2-8 | 22-41-11 | D41355J | 18 | | | D00079A | K01 | | | 001-099 |
| 5012B | 24 | G2 | AR | | 3-0 | 22-41-11 | D41355J | 18 | | | D00079A | K01 | | | 115-199 |
| 5012R | 24 | G2 | AR | | 0-0 | 22-41-11 | D41355J | 17 | | | D00079A | J01 | | | ALL |
| 5012Z | | | AR | | 0-0 | 22-41-11 | D41355J | | | AK | D00079A | DED | | | ALL |
| 5013B | 24 | G2 | AS | | 2-5 | 22-41-11 | D41401J | 1 | | | D00079A | B01 | | | 001-099 |
| 5013B | 24 | G2 | AS | | 3-0 | 22-41-11 | D41401J | 1 | | | D00079A | B01 | | | 115-199 |
| 5013R | 24 | G2 | AS | | 0-0 | 22-41-11 | D41401J | 2 | | | D00079A | A01 | | | ALL |
| 5013Z | | | AS | | 0-0 | 22-41-11 | D41401J | | | AL | D00079A | DED | | | ALL |
| 5014B | 24 | G2 | AT | | 2-9 | 22-41-11 | D41303J | 9 | | | D00079A | B03 | | | 001-099 |
| 5014B | 24 | G2 | AT | | 3-0 | 22-41-11 | D41303J | 9 | | | D00079A | B03 | | | 115-199 |
| 5014R | 24 | G2 | AT | | 0-0 | 22-41-11 | D41303J | 8 | | | D00079A | A03 | | | ALL |
| 5014Z | | | AT | | 0-0 | 22-41-11 | D41303J | | | AM | D00079A | DED | | | ALL |
| 5015B | 24 | G2 | AU | | 2-9 | 22-41-11 | D41303J | 18 | | | D00079A | B04 | | | 001-099 |
| 5015B | 24 | G2 | AU | | 3-0 | 22-41-11 | D41303J | 18 | | | D00079A | B04 | | | 115-199 |
| 5015R | 24 | G2 | AU | | 0-0 | 22-41-11 | D41303J | 17 | | | D00079A | A04 | | | ALL |
| 5015Z | | | AU | | 0-0 | 22-41-11 | D41303J | | | AN | D00079A | DED | | | ALL |
| 5016B | 24 | G2 | AV | | 2-8 | 22-41-11 | D41355J | 32 | | | D00079A | K04 | | | 001-099 |
| 5016B | 24 | G2 | AV | | 3-0 | 22-41-11 | D41355J | 32 | | | D00079A | K04 | | | 115-199 |
| 5016R | 24 | G2 | AV | | 0-0 | 22-41-11 | D41355J | 31 | | | D00079A | J04 | | | ALL |
| 5016Z | | | AV | | 0-0 | 22-41-11 | D41355J | | | AP | D00079A | DED | | | ALL |
| 5017B | 24 | G2 | AW | | 2-9 | 22-41-12 | D41303J | 20 | | | D00079A | B09 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5017B | 24 | G2 | AW | | 3-0 | 22-41-12 | D41303J | 20 | | | D00079A | B09 | | | 115-199 |
| 5017R | 24 | G2 | AW | | 0-0 | 22-41-12 | D41303J | 19 | | | D00079A | A09 | | | ALL |
| 5017Z | | | AW | | 0-0 | 22-41-12 | D41303J | | | AQ | D00079A | DED | | | ALL |
| 5018B | 24 | G2 | AX | | 2-9 | 22-41-12 | D41303J | 23 | | | D00079A | B10 | | | 001-099 |
| 5018B | 24 | G2 | AX | | 3-0 | 22-41-12 | D41303J | 23 | | | D00079A | B10 | | | 115-199 |
| 5018R | 24 | G2 | AX | | 0-0 | 22-41-12 | D41303J | 22 | | | D00079A | A10 | | | ALL |
| 5018Z | | | AX | | 0-0 | 22-41-12 | D41303J | | | AR | D00079A | DED | | | ALL |
| 5019B | 24 | G2 | AY | | 2-9 | 22-41-13 | D41303J | 32 | | | TB0137Y | C072 | BJ | | 001-099 |
| 5019B | 24 | G2 | AY | | 3-0 | 22-41-13 | D41303J | 32 | | | TB0137Y | C072 | BJ | | 115-199 |
| 5019R | 24 | G2 | AY | | 0-0 | 22-41-13 | D41303J | 31 | | | TB0137Y | A072 | BJ | | ALL |
| 5019Z | | | AY | | 0-0 | 22-41-13 | D41303J | 33 | | | GD01930 | ST.. | 2 | | ALL |
| 5020B | 24 | G2 | AZ | | 2-2 | 22-41-13 | D00079A | K15 | | | TB0137Y | C072 | BJ | | 001-099 |
| 5020B | 24 | G2 | AZ | | 3-0 | 22-41-13 | D00079A | K15 | | | TB0137Y | C072 | BJ | | 115-199 |
| 5020R | 24 | G2 | AZ | | 0-0 | 22-41-13 | D00079A | J15 | | | TB0137Y | A072 | BJ | | ALL |
| 5020Z | | | AZ | | 0-0 | 22-41-13 | D00079A | DED | | | GD01930 | ST.. | 2 | | ALL |
| 5021B | 24 | G2 | BA | | 2-2 | 22-41-12 | D00079A | B11 | | | TB0137Y | C071 | BJ | | 001-099 |
| 5021B | 24 | G2 | BA | | 3-0 | 22-41-12 | D00079A | B11 | | | TB0137Y | C071 | BJ | | 115-199 |
| 5021R | 24 | G2 | BA | | 0-0 | 22-41-12 | D00079A | A11 | | | TB0137Y | A071 | BJ | | ALL |
| 5021Z | | | BA | | 0-0 | 22-41-12 | D00079A | DED | | | GD01930 | ST.. | 2 | | ALL |
| 5022B | 24 | G2 | BB | | 2-9 | 22-41-12 | D41303J | 26 | | | TB0137Y | C071 | BJ | | 001-099 |
| 5022B | 24 | G2 | BB | | 3-0 | 22-41-12 | D41303J | 26 | | | TB0137Y | C071 | BJ | | 115-199 |
| 5022R | 24 | G2 | BB | | 0-0 | 22-41-12 | D41303J | 25 | | | TB0137Y | A071 | BJ | | ALL |
| 5022Z | | | BB | | 0-0 | 22-41-12 | D41303J | 27 | | | GD01930 | ST.. | 2 | | ALL |
| 5023B | 24 | G2 | BC | | 2-9 | 22-41-12 | D41303J | 29 | | | TB0137Y | C071 | BJ | | 001-099 |
| 5023B | 24 | G2 | BC | | 3-0 | 22-41-12 | D41303J | 29 | | | TB0137Y | C071 | BJ | | 115-199 |
| 5023R | 24 | G2 | BC | | 0-0 | 22-41-12 | D41303J | 28 | | | TB0137Y | A071 | BJ | | ALL |
| 5023Z | | | BC | | 0-0 | 22-41-12 | D41303J | 30 | | | GD01930 | ST.. | 2 | | ALL |
| 5024B | 24 | G2 | BF | | 2-3 | 22-41-13 | D41741J | 2 | | | TB0137Y | C072 | BJ | | 001-099 |
| 5024B | 24 | G2 | BF | | 3-0 | 22-41-13 | D41741J | 2 | | | TB0137Y | C072 | BJ | | 115-199 |
| 5024R | 24 | G2 | BF | | 0-0 | 22-41-13 | D41741J | 1 | | | TB0137Y | A072 | BJ | | ALL |
| 5024Z | | | BF | | 0-0 | 22-41-13 | D41741J | 3 | | | GD01930 | ST.. | 2 | | ALL |
| 5101B | 24 | G2 | BK | | 2-3 | 34-51-11 | D43001J | 9 | | | D00231B | C09 | | | 001-099 |
| 5101R | 24 | G2 | BK | | 0-0 | 34-51-11 | D43001J | 8 | | | D00231B | B09 | | | 001-099 |
| 5101Z | | | BK | | 0-0 | 34-51-11 | D43001J | | | BK | D00231B | DED | | | 001-099 |
| 5102B | 24 | G2 | BL | | 1-8 | 34-51-11 | D43009J | 2 | | | D00231B | C11 | | | 001-099 |
| 5102R | 24 | G2 | BL | | 0-0 | 34-51-11 | D43009J | 1 | | | D00231B | B11 | | | 001-099 |
| 5102Z | | | BL | | 0-0 | 34-51-11 | D43009J | | | BL | D00231B | DED | | | 001-099 |
| 5103B | 24 | G2 | BM | | 2-3 | 34-51-11 | D43001J | 6 | | | D00231B | B04 | | | 001-099 |
| 5103R | 24 | G2 | BM | | 0-0 | 34-51-11 | D43001J | 5 | | | D00231B | A04 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5103Z | | | | BM | 0-0 | 34-51-11 | D43001J | | | | BM | D00231B | DED | | 001-099 |
| 5104B | 24 | G2 | | BN | 2-3 | 34-22-19 | D43001J | 2 | | | | D00231B | C13 | | 001-099 |
| 5104R | 24 | G2 | | BN | 0-0 | 34-22-19 | D43001J | 1 | | | | D00231B | B13 | | 001-099 |
| 5104Z | | | | BN | 0-0 | 34-22-19 | D43001J | | | | BN | D00231B | DED | | 001-099 |
| 5201B | 24 | G2 | | CK | 1-11 | 34-51-21 | D43005J | 3 | | | | D00235B | C09 | | 001-099 |
| 5201R | 24 | G2 | | CK | 0-0 | 34-51-21 | D43005J | 2 | | | | D00235B | B09 | | 001-099 |
| 5201Z | | | | CK | 0-0 | 34-51-21 | D43005J | | | | CK | D00235B | DED | | 001-099 |
| 5202B | 24 | G2 | | CL | 4-7 | 34-51-21 | D42091J | 30 | | | | D00235B | C11 | | 001-099 |
| 5202R | 24 | G2 | | CL | 0-0 | 34-51-21 | D42091J | 29 | | | | D00235B | B11 | | 001-099 |
| 5202Z | | | | CL | 0-0 | 34-51-21 | D42091J | | | | CL | D00235B | DED | | 001-099 |
| 5203B | 24 | G2 | | CM | 1-11 | 34-51-21 | D43005J | 6 | | | | D00235B | B04 | | 001-099 |
| 5203R | 24 | G2 | | CM | 0-0 | 34-51-21 | D43005J | 5 | | | | D00235B | A04 | | 001-099 |
| 5203Z | | | | CM | 0-0 | 34-51-21 | D43005J | | | | CM | D00235B | DED | | 001-099 |
| 5204B | 24 | G2 | | CN | 1-11 | 34-22-29 | D43005J | 10 | | | | D00235B | C13 | | 001-099 |
| 5204R | 24 | G2 | | CN | 0-0 | 34-22-29 | D43005J | 9 | | | | D00235B | B13 | | 001-099 |
| 5204Z | | | | CN | 0-0 | 34-22-29 | D43005J | | | | CN | D00235B | DED | | 001-099 |
| 5210B | 24 | G2 | | BR | 2-8 | 34-22-91 | D42091J | 9 | | | | D45005J | 12 | | 001-099 |
| 5210R | 24 | G2 | | BR | 0-0 | 34-22-91 | D42091J | 8 | | | | D45005J | 13 | | 001-099 |
| 5210Z | | | | BR | 0-0 | 34-22-91 | D42091J | 10 | | | | D45005J | 14 | | 001-099 |
| 5211B | 24 | G2 | | BO | 3-8 | 23-51-13 | D43001J | 13 | | | | D45001J | 3 | | 001-099 |
| 5211R | 24 | G2 | | BO | 0-0 | 23-51-13 | D43001J | 12 | | | | D45001J | 4 | | 001-099 |
| 5211Z | | | | BO | 0-0 | 23-51-13 | D43001J | 14 | | | | D45001J | 5 | | 001-099 |
| 5212B | 24 | G2 | | BP | 5-5 | 23-51-13 | D43005J | 13 | | | | D45005J | 3 | | 001-099 |
| 5212R | 24 | G2 | | BP | 0-0 | 23-51-13 | D43005J | 12 | | | | D45005J | 4 | | 001-099 |
| 5212Z | | | | BP | 0-0 | 23-51-13 | D43005J | 14 | | | | D45005J | 5 | | 001-099 |
| 5214B | 24 | G2 | | CO | 3-6 | 34-22-81 | D43009J | 12 | | | | D45001J | 12 | | 001-099 |
| 5214R | 24 | G2 | | CO | 0-0 | 34-22-81 | D43009J | 11 | | | | D45001J | 13 | | 001-099 |
| 5214Z | | | | CO | 0-0 | 34-22-81 | D43009J | 13 | | | | D45001J | 14 | | 001-099 |
| 5225B | 24 | G2 | | DV | 6-0 | 34-45-02 | D00253A | F05 | | | | D43005J | 27 | | 001-099 |
| 5225B | 24 | G2 | | DV | 7-0 | 34-45-02 | D00253A | F05 | | | | D43005J | 2 | | 115-199 |
| 5225R | 24 | G2 | | DV | 0-0 | 34-45-02 | D00253A | E05 | | | | D43005J | 26 | | 001-099 |
| 5225R | 24 | G2 | | DV | 0-0 | 34-45-02 | D00253A | E05 | | | | D43005J | 1 | | 115-199 |
| 5225Z | | | | DV | 0-0 | 34-45-02 | D00253A | DED | | | | D43005J | | DV | ALL |
| 5226B | 24 | G2 | | DW | 6-0 | 34-45-02 | D00253A | H05 | | | | D43005J | 30 | | 001-099 |
| 5226B | 24 | G2 | | DW | 7-0 | 34-45-02 | D00253A | H05 | | | | D43005J | 5 | | 115-199 |
| 5226R | 24 | G2 | | DW | 0-0 | 34-45-02 | D00253A | G05 | | | | D43005J | 29 | | 001-099 |
| 5226R | 24 | G2 | | DW | 0-0 | 34-45-02 | D00253A | G05 | | | | D43005J | 4 | | 115-199 |
| 5226Z | | | | DW | 0-0 | 34-45-02 | D00253A | DED | | | | D43005J | | DW | ALL |
| FRAA | | | | | 0-0 | 34-53-21 | D41527J | | | AA | | D41527J | 21 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1423 | 286N1423 | | | E3-2 SHELF BUNDLE (continued) | | | | | | | | | | |
| FRAA | | | | 0-0 | 34-53-21 | D41527J | | | | AA | D41527J | 14 | | 115-199 |
| FRAB | | | | 0-0 | 34-53-21 | D41303J | | | | AB | D41303J | 3 | | ALL |
| FRAC | | | | 0-0 | 34-53-21 | D41355J | | | | AC | D41355J | 12 | | ALL |
| FRAF | | | | 0-0 | 34-55-21 | D42091J | | | | AF | D42091J | 20 | | ALL |
| FRAG | | | | 0-0 | 34-55-21 | D41355J | | | | AG | D41355J | 29 | | ALL |
| FRAH | | | | 0-0 | 34-61-13 | D41355J | | | | AH | D41355J | 6 | | ALL |
| FRAI | | | | 0-0 | 34-22-29 | D41355J | | | | AI | D41355J | 9 | | ALL |
| FRAJ | | | | 0-0 | 22-41-11 | D41303J | | | | AJ | D41303J | 13 | | ALL |
| FRAK | | | | 0-0 | 22-41-11 | D41355J | | | | AK | D41355J | 19 | | ALL |
| FRAL | | | | 0-0 | 22-41-11 | D41401J | | | | AL | D41401J | 3 | | ALL |
| FRAM | | | | 0-0 | 22-41-11 | D41303J | | | | AM | D41303J | 10 | | ALL |
| FRAN | | | | 0-0 | 22-41-11 | D41303J | | | | AN | D41303J | 16 | | ALL |
| FRAP | | | | 0-0 | 22-41-11 | D41355J | | | | AP | D41355J | 33 | | ALL |
| FRAQ | | | | 0-0 | 22-41-12 | D41303J | | | | AQ | D41303J | 21 | | ALL |
| FRAR | | | | 0-0 | 22-41-12 | D41303J | | | | AR | D41303J | 24 | | ALL |
| FRBK | | | | 0-0 | 34-51-11 | D43001J | | | | BK | D43001J | 10 | | 001-099 |
| FRBL | | | | 0-0 | 34-51-11 | D43009J | | | | BL | D43009J | 3 | | 001-099 |
| FRBM | | | | 0-0 | 34-51-11 | D43001J | | | | BM | D43001J | 7 | | 001-099 |
| FRBN | | | | 0-0 | 34-22-19 | D43001J | | | | BN | D43001J | 3 | | 001-099 |
| FRCA | | | | 0-0 | 23-11-21 | D42045J | | | | CA | D42045J | 11 | | 001-099 |
| FRCK | | | | 0-0 | 34-51-21 | D43005J | | | | CK | D43005J | 4 | | 001-099 |
| FRCL | | | | 0-0 | 34-51-21 | D42091J | | | | CL | D42091J | 31 | | 001-099 |
| FRCM | | | | 0-0 | 34-51-21 | D43005J | | | | CM | D43005J | 7 | | 001-099 |
| FRCN | | | | 0-0 | 34-22-29 | D43005J | | | | CN | D43005J | 11 | | 001-099 |
| FRDV | | | | 0-0 | 34-45-02 | D43005J | | 28 | | | D43005J | | DV | 001-099 |
| FRDV | | | | 0-0 | 34-45-02 | D43005J | | 3 | | | D43005J | | DV | 115-199 |
| FRDW | | | | 0-0 | 34-45-02 | D43005J | | 31 | | | D43005J | | DW | 001-099 |
| FRDW | | | | 0-0 | 34-45-02 | D43005J | | 6 | | | D43005J | | DW | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1420

Page 12 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------|-------|----------|---------|------|------|--------|--------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE | | | | | | | | | | | |
| 0001 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | A01 | | D00751 | 1 | VP | | 001-010 |
| 0001 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | A01 | | D00751 | 1 | VP | | 011-099 |
| 0001 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | A01 | | D00751 | 1 | | | 115-199 |
| 0002 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | B01 | | D00751 | 2 | | | 001, 004-010 |
| 0002 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | B01 | | D00751 | 2 | VP | | 002-003 |
| 0002 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | B01 | | D00751 | 2 | | | 011-099 |
| 0002 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | B01 | | D00751 | 2 | VP | | 115-199 |
| 0003 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | C01 | | D00751 | 3 | VP | | 001-004, 006, 009-010 |
| 0003 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | C01 | | D00751 | 3 | | | 005, 007-008 |
| 0003 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | C01 | | D00751 | 3 | VP | | 011-099 |
| 0003 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | C01 | | D00751 | 3 | | | 115-199 |
| 0004 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | D01 | | D00751 | 4 | VP | | 001-004, 006, 009-010 |
| 0004 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | D01 | | D00751 | 4 | | | 005, 007-008 |
| 0004 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | D01 | | D00751 | 4 | VP | | 011-099 |
| 0004 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | D01 | | D00751 | 4 | VP | | 115-199 |
| 0005 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | E01 | | D00751 | 5 | VP | | 001, 009 |
| 0005 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | E01 | | D00751 | 5 | | | 002-008, 010 |
| 0005 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | E01 | | D00751 | 5 | | | 011-099 |
| 0005 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | E01 | | D00751 | 5 | | | 115-199 |
| 0006 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | F01 | | D00751 | 6 | VP | | 001, 005, 007-009 |
| 0006 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | F01 | | D00751 | 6 | | | 002-004, 006, 010 |
| 0006 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | F01 | | D00751 | 6 | | | 011-099 |
| 0006 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | F01 | | D00751 | 6 | VP | | 115-199 |
| 0007 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | G01 | | D00751 | 7 | VP | | 001-010 |
| 0007 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | G01 | | D00751 | 7 | VP | | 011-099 |
| 0007 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | G01 | | D00751 | 7 | | | 115-199 |
| 0008 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | H01 | | D00751 | 8 | VP | | 001, 004-010 |
| 0008 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | H01 | | D00751 | 8 | | | 002-003 |
| 0008 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | H01 | | D00751 | 8 | VP | | 011-099 |
| 0008 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | H01 | | D00751 | 8 | VP | | 115-199 |
| 0009 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | J01 | | D00751 | 9 | VP | | 001-003, 005, 007-009 |
| 0009 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | J01 | | D00751 | 9 | | | 004, 006, 010 |
| 0009 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | J01 | | D00751 | 9 | | | 011-099 |
| 0009 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | J01 | | D00751 | 9 | VP | | 115-199 |
| 0010 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | K01 | | D00751 | 10 | VP | | 001-010 |
| 0010 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | | K01 | | D00751 | 10 | VP | | 011-099 |
| 0010 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | | K01 | | D00751 | 10 | VP | | 115-199 |
| 0011 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | A02 | | D00751 | 11 | VP | | 001-003, 005, 007-009 |
| 0011 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | | A02 | | D00751 | 11 | | | 004, 006, 010 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--------------------------------------|-------|----------|---------|-------|------|--------|---------|------|------|--------|------------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0011 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | A02 | | | D00751 | 11 | | | 011-099 |
| 0011 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | A02 | | | D00751 | 11 | | | 115-199 |
| 0012 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | B02 | | | D00751 | 12 | VP | | 001-010 |
| 0012 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | B02 | | | D00751 | 12 | VP | | 011-099 |
| 0012 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | B02 | | | D00751 | 12 | | | 115-199 |
| 0013 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | C02 | | | D00751 | 13 | VP | | 001-010 |
| 0013 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | C02 | | | D00751 | 13 | VP | | 011-099 |
| 0013 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | C02 | | | D00751 | 13 | VP | | 115-199 |
| 0014 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | D02 | | | D00751 | 14 | | | 001, 009 |
| 0014 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | D02 | | | D00751 | 14 | VP | | 002-008, 010 |
| 0014 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | D02 | | | D00751 | 14 | VP | | 011-099 |
| 0014 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | D02 | | | D00751 | 14 | | | 115-199 |
| 0015 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | E02 | | | D00751 | 15 | VP | | 001-010 |
| 0015 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | E02 | | | D00751 | 15 | VP | | 011-099 |
| 0015 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | E02 | | | D00751 | 15 | VP | | 115-199 |
| 0016 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | F02 | | | D00751 | 16 | VP | | 001-008, 010 |
| 0016 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | F02 | | | D00751 | 16 | | | 009 |
| 0016 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | F02 | | | D00751 | 16 | VP | | 011-099 |
| 0016 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | F02 | | | D00751 | 16 | VP | | 115-199 |
| 0017 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | G02 | | | D00751 | 17 | | | 001 |
| 0017 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | G02 | | | D00751 | 17 | VP | | 002-010 |
| 0017 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | G02 | | | D00751 | 17 | VP | | 011-099 |
| 0017 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | G02 | | | D00751 | 17 | VP | | 115-199 |
| 0018 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | H02 | | | D00751 | 18 | | | 001, 004, 006, 010 |
| 0018 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | H02 | | | D00751 | 18 | VP | | 002-003, 005, 007-009 |
| 0018 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | H02 | | | D00751 | 18 | | | 011-099 |
| 0018 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | H02 | | | D00751 | 18 | | | 115-199 |
| 0019 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | J02 | | | D00751 | 19 | | | 001-003, 005, 007-010 |
| 0019 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | J02 | | | D00751 | 19 | VP | | 004, 006 |
| 0019 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | J02 | | | D00751 | 19 | | | 011-099 |
| 0019 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | J02 | | | D00751 | 19 | | | 115-199 |
| 001CO | | | | AF | 0-0 | 34-53-11 | D00251B | = C71 | | | D41753J | = C1 | | | ALL |
| 001CX | | | JB | AF | 1-11 | 34-53-11 | D00251B | 71 | | | D41753J | = A1 | | | 001-099 |
| 001CX | | | JB | AF | 1-10 | 34-53-11 | D00251B | 71 | | | D41753J | = A1 | | | 115-199 |
| 0020 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | K02 | | | D00751 | 20 | | | 001, 003, 005, 009 |
| 0020 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | K02 | | | D00751 | 20 | VP | | 002, 004, 006-008, 010 |
| 0020 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | K02 | | | D00751 | 20 | VP | | 011-099 |
| 0020 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | K02 | | | D00751 | 20 | VP | | 115-199 |
| 0021 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | A03 | | | D00751 | 21 | VP | | 001-002, 004-005, 009 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | | | |
|------------------------|-------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|----------------------------|--|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W1433 | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | | | |
| 0021 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | A03 | | | D00751 | 21 | | | 003, 006-008, 010 | | | |
| 0021 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | A03 | | | D00751 | 21 | | | 011-099 | | | |
| 0021 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | A03 | | | D00751 | 21 | | | 115-199 | | | |
| 0022 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | B03 | | | D00751 | 22 | VP | | 001-002, 005-006, 009-010 | | | |
| 0022 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | B03 | | | D00751 | 22 | | | 003-004, 007-008 | | | |
| 0022 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | B03 | | | D00751 | 22 | VP | | 011-099 | | | |
| 0022 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | B03 | | | D00751 | 22 | | | 115-199 | | | |
| 0023 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | C03 | | | D00751 | 23 | VP | | 001, 003, 006-007, 010 | | | |
| 0023 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | C03 | | | D00751 | 23 | | | 002, 004-005, 008-009 | | | |
| 0023 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | C03 | | | D00751 | 23 | VP | | 011-099 | | | |
| 0023 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | C03 | | | D00751 | 23 | | | 115-199 | | | |
| 0024 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | D03 | | | D00751 | 24 | VP | | 001-002, 005-006, 008, 010 | | | |
| 0024 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | D03 | | | D00751 | 24 | | | 003-004, 007, 009 | | | |
| 0024 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | D03 | | | D00751 | 24 | | | 011-099 | | | |
| 0024 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | D03 | | | D00751 | 24 | VP | | 115-199 | | | |
| 0025 | 24 | | GK | | 2-4 | 34-53-12 | D00251B | E03 | | | D00751 | 25 | | | 001-010 | | | |
| 0025 | 24 | | GK | | 3-0 | 34-53-12 | D00251B | E03 | | | D00751 | 25 | | | 011-099 | | | |
| 0025 | 24 | | GK | | 2-0 | 34-53-12 | D00251B | E03 | | | D00751 | 25 | | | 115-199 | | | |
| 0026 | 24 | | GK | | 3-6 | 34-53-11 | D00251B | H03 | | | D41525J | 9 | | | 001-002 | | | |
| 0026 | 24 | | GK | | 4-0 | 34-53-11 | D00251B | H03 | | | D41525J | 9 | | | 115-199 | | | |
| 0027 | 24 | | GK | | 3-6 | 34-53-11 | D00251B | J03 | | | D41525J | 19 | | | 001-002 | | | |
| 0027 | 24 | | GK | | 4-0 | 34-53-11 | D00251A | E07 | | | D41525J | 10 | | | 115-199 | | | |
| 0028 | 24 | | GK | | 3-6 | 34-53-11 | D00251B | K03 | | | D41525J | 20 | | | 001-099 | | | |
| 0028 | 24 | | GK | | 4-0 | 34-53-11 | D00251B | K03 | | | D41525J | 2 | | | 115-199 | | | |
| 0029 | 22 | | GA | | 4-0 | 34-53-11 | D42019J | 5 | | | TB0181A | C001 | 2 | | 115-199 | | | |
| 002CO | | | | AG | 0-0 | 34-53-11 | D00251C | =C12 | | | D02138 | =C1 | | | ALL | | | |
| 002CX | | 66 | | AG | 1-1 | 34-53-11 | D00251C | 12 | | | D02138 | =A1 | | | 001-099 | | | |
| 002CX | | 66 | | AG | 1-2 | 34-53-11 | D00251C | 12 | | | D02138 | =A1 | | | 115-199 | | | |
| 0030 | 24 | | GK | | 2-2 | 34-53-11 | D41443J | 26 | | | D41525J | 10 | | | 001-099 | | | |
| 0030 | 24 | | GK | | 3-0 | 34-53-11 | D41309J | 48 | | | D41525J | 8 | | | 115-199 | | | |
| 0031 | 20 | | GA | | 1-6 | 34-53-11 | D41525J | | | AA | GD01947 | ST.. | 2 | | 001-099 | | | |
| 0031 | 22 | | GA | | 4-0 | 34-53-11 | D00251B | E06 | | | TB0181A | A001 | 2 | | 115-199 | | | |
| 0032 | 20 | | GA | | 1-6 | 34-53-11 | D41309J | | | AB | GD01944 | ST.. | 2 | | 001-002 | | | |
| 0032 | 20 | | GA | | 2-2 | 34-53-11 | D41309J | | | AB | GD03366 | ST.. | 2 | | 003-099 | | | |
| 0032 | 20 | | GA | | 1-6 | 34-53-11 | D41309J | | | AB | GD01947 | ST.. | 2 | | 115-199 | | | |
| 0033 | 20 | | GA | | 1-6 | 34-53-11 | D41361J | | | AC | GD01949 | ST.. | 2 | | 001-099 | | | |
| 0033 | 20 | | GA | | 1-6 | 34-53-11 | D41361J | | | AC | GD01947 | ST.. | 2 | | 115-199 | | | |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|-------------------------------|-------|-------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1433 | 286N1433 | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | | | |
| 0034 | 22 | GA | | | 2-0 | 34-53-11 | D00251B | J05 | | | D00751 | 29 | | | 115-199 |
| 0036 | 24 | GK | | | 2-2 | 34-53-11 | D41525J | 24 | | | D41443J | 25 | | | 001-099 |
| 0036 | 24 | GK | | | 2-0 | 34-53-11 | D41525J | 12 | | | D41443J | 25 | | | 115-199 |
| 0037 | 22 | GA | | | 3-5 | 34-53-11 | D00251C | 1 | | | D41525J | 13 | | | 001-099 |
| 0037 | 22 | GA | | | 4-0 | 34-53-11 | D00251C | 1 | | | D41525J | 5 | | | 115-199 |
| 0038 | 20 | GA | | | 2-2 | 34-53-11 | D00251C | 7 | | | GD01941 | AC.. | 2 | | 001-099 |
| 0038 | 20 | GA | | | 2-0 | 34-53-11 | D00251C | 7 | | | GD01941 | AC.. | 2 | | 115-199 |
| 0039 | 20 | GA | | | 2-2 | 34-53-11 | D00251C | 11 | | | GD01941 | ST.. | 2 | | 001-099 |
| 0039 | 20 | GA | | | 2-0 | 34-53-11 | D00251C | 11 | | | GD01941 | ST.. | 2 | | 115-199 |
| 003CO | | | AI | | 0-0 | 34-55-11 | D00239B | = C71 | | | D42145J | = C1 | | | ALL |
| 003CX | | JB | AI | | 1-10 | 34-55-11 | D00239B | 71 | | | D42145J | = A1 | | | ALL |
| 0040 | 20 | GA | | | 2-2 | 34-53-11 | D00251C | 8 | | | GD01941 | DC.. | 2 | | 001-099 |
| 0041 | 22 | GA | | | 2-1 | 34-55-11 | D00239C | 1 | | | D40678J | 9 | | | 001-099 |
| 0041 | 22 | GA | | | 3-0 | 34-55-11 | D00239C | 1 | | | D42019J | 22 | | | 115-199 |
| 0042 | 20 | GA | | | 1-11 | 34-55-11 | D00239C | 7 | | | GD01943 | AC.. | 2 | | 001-099 |
| 0042 | 20 | GA | | | 2-0 | 34-55-11 | D00239C | 7 | | | GD01943 | AC.. | 2 | | 115-199 |
| 0043 | 20 | GA | | | 1-11 | 34-55-11 | D00239C | 11 | | | GD01943 | ST.. | 2 | | 001-099 |
| 0043 | 20 | GA | | | 2-0 | 34-55-11 | D00239C | 11 | | | GD01943 | ST.. | 2 | | 115-199 |
| 0044 | 24 | GK | | | 3-2 | 34-55-11 | SM00001 | | WI | | D42019J | 14 | | | 001-099 |
| 0044 | 24 | GK | | | 3-0 | 34-55-11 | SM00001 | | WI | | D42019J | 14 | | | 115-199 |
| 0045 | 24 | GK | | | 2-7 | 34-55-11 | SM00001 | | WI | | D00239B | B05 | | | 001-099 |
| 0045 | 24 | GK | | | 2-0 | 34-55-11 | SM00001 | | WI | | D00239B | B05 | | | 115-199 |
| 0046 | 24 | GK | | | 2-5 | 34-61-23 | SM00001 | | WI | | D41309J | 17 | | | 001-099 |
| 0046 | 24 | GK | | | 2-0 | 34-61-23 | SM00001 | | WI | | D41309J | 17 | | | 115-199 |
| 0047 | 24 | GK | | | 2-2 | 23-51-12 | D00239B | B01 | | | D41309J | 37 | | | 001-099 |
| 0047 | 24 | GK | | | 3-0 | 23-51-12 | D00239B | B01 | | | D41309J | 37 | | | 115-199 |
| 0048 | 24 | GK | | | 2-5 | 23-51-12 | D00239B | A01 | | | D42019J | 17 | | | 001-099 |
| 0048 | 24 | GK | | | 3-0 | 23-51-12 | D00239B | A01 | | | D42019J | 17 | | | 115-199 |
| 0049 | 22 | GA | | | 2-5 | 23-51-12 | D41309J | 40 | | | GD01944 | ST.. | 2 | | 001-099 |
| 0049 | 22 | GA | | | 3-0 | 23-51-12 | D41309J | 40 | | | GD01944 | ST.. | 2 | | 115-199 |
| 004CO | | | AJ | | 0-0 | 34-55-11 | D00239C | = C12 | | | D02128 | = C1 | | | ALL |
| 004CX | | 66 | AJ | | 0-10 | 34-55-11 | D00239C | 12 | | | D02128 | = A1 | | | 001-099 |
| 004CX | | 66 | AJ | | 1-4 | 34-55-11 | D00239C | 12 | | | D02128 | = A1 | | | 115-199 |
| 0050 | 22 | GA | | | 2-4 | 23-51-12 | D42019J | 18 | | | GD01944 | ST.. | 2 | | 001-099 |
| 0050 | 22 | GA | | | 3-0 | 23-51-12 | D42019J | 18 | | | GD01944 | ST.. | 2 | | 115-199 |
| 0051 | 24 | GK | | | 2-2 | 34-55-11 | D41309J | 41 | | | D00239B | K05 | | | 001-099 |
| 0051 | 24 | GK | | | 3-0 | 34-55-11 | D41309J | 41 | | | D00239B | K05 | | | 115-199 |
| 0052 | 22 | GA | | | 2-1 | 34-55-11 | D00239B | D05 | | | GD01943 | DC.. | 2 | | 001-099 |
| 0052 | 24 | GK | | | 3-0 | 34-55-11 | D00239B | D05 | | | D42019J | 26 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------|-------------------------------|----------|---------|-------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | |
| 0053 | 22 | | GA | | 2-1 | 34-55-11 | D00239B | E05 | | | GD01943 | DC.. | 2 | | 001-099 |
| 0053 | 24 | | GK | | 3-0 | 34-55-11 | D00239B | E05 | | | D42071J | 12 | | | 115-199 |
| 0054 | 24 | | GK | | 2-5 | 34-53-12 | D00251A | C05 | | | TB0181Y | A003 | BJ | | 001-099 |
| 0054 | 24 | | GK | | 2-0 | 34-53-12 | D00251A | C05 | | | D00751 | 27 | | | 115-199 |
| 0055 | 24 | | GK | | 2-5 | 34-53-12 | D00251A | D05 | | | TB0181Y | A003 | BJ | | 001-099 |
| 0055 | 24 | | GK | | 2-0 | 34-53-12 | D00251A | D05 | | | D00751 | 28 | | | 115-199 |
| 0056 | 20 | | GA | | 1-6 | 34-55-11 | D42019J | | | AF | GD01944 | ST.. | 2 | | 001-099 |
| 0056 | 20 | | GA | | 1-6 | 34-55-11 | D42019J | | | AF | GD01942 | ST.. | 2 | | 115-199 |
| 0057 | 20 | | GA | | 1-6 | 34-55-11 | D41309J | | | AG | GD01944 | ST.. | 2 | | 001-002, 115-199 |
| 0057 | 20 | | GA | | 2-2 | 34-55-11 | D41309J | | | AG | GD03366 | ST.. | 2 | | 003-099 |
| 0058 | 20 | | GA | | 1-6 | 34-61-12 | D41309J | | | AH | GD01944 | ST.. | 2 | | 001-002, 115-199 |
| 0058 | 20 | | GA | | 2-2 | 34-61-12 | D41309J | | | AH | GD03366 | ST.. | 2 | | 003-099 |
| 0059 | 20 | | GA | | 1-6 | 34-22-19 | D41309J | | | AI | GD01944 | ST.. | 2 | | 001-002, 115-199 |
| 0059 | 20 | | GA | | 2-2 | 34-22-19 | D41309J | | | AI | GD03366 | ST.. | 2 | | 003-099 |
| 005CO | | | | AK | 0-0 | 34-53-11 | D00251A | = C71 | | | D41851J | = C1 | | | ALL |
| 005CX | | | JB | AK | 1-10 | 34-53-11 | D00251A | 71 | | | D41851J | = A1 | | | ALL |
| 0060 | 20 | | GA | | 1-11 | 22-41-11 | D40678J | 5 | | | D41309J | 46 | | | 001-099 |
| 0060 | 20 | | GA | | 3-0 | 22-41-11 | D40678J | 5 | | | D41309J | 46 | | | 115-199 |
| 0061 | 22 | | GA | | 2-5 | 31-31-01 | D40678J | 4 | | | SM00072 | | WI | | 001-099 |
| 0061 | 22 | | GA | | 5-0 | 31-31-11 | D40678J | 4 | | | TB0181Z | 105 | BJ | | 115-199 |
| 0062 | 22 | | GA | | 3-11 | 31-31-01 | D40678J | 3 | | | TB0181Z | 106 | BJ | | 001-099 |
| 0062 | 22 | | GA | | 5-0 | 31-31-11 | D40678J | 3 | | | TB0181Z | 106 | BJ | | 115-199 |
| 0063 | 22 | | GA | | 2-5 | 31-31-01 | D41519J | 1 | | | TB0181Z | 106 | BJ | | 001-099 |
| 0063 | 22 | | GA | | 3-0 | 31-31-11 | D41519J | 1 | | | TB0181Z | 106 | BJ | | 115-199 |
| 0064 | 22 | | GA | | 3-0 | 31-31-11 | D41519J | 4 | | | TB0181Z | 107 | BJ | | 115-199 |
| 0065 | 22 | | GA | | 2-5 | 31-31-01 | D41519J | 2 | | | TB0181Z | 108 | BJ | | 001-099 |
| 0065 | 22 | | GA | | 3-0 | 31-31-11 | D41519J | 2 | | | TB0181Z | 108 | BJ | | 115-199 |
| 0066 | 22 | | GA | | 4-2 | 31-31-01 | SM00072 | | WI | | SM00069 | | WI | | 001-099 |
| 0068 | 22 | | GA | | 3-8 | 31-31-01 | D41443J | 6 | | | TB0181Z | 106 | BJ | | 001-099 |
| 0068 | 22 | | GA | | 4-0 | 31-31-11 | D41443J | 6 | | | TB0181Z | 106 | BJ | | 115-199 |
| 0069 | 22 | | GA | | 3-8 | 31-31-01 | D41443J | 7 | | | TB0181Z | 108 | BJ | | 001-099 |
| 0069 | 22 | | GA | | 4-0 | 31-31-11 | D41443J | 7 | | | TB0181Z | 108 | BJ | | 115-199 |
| 0070 | 22 | | GA | | 2-9 | 31-31-01 | D41443J | 1 | | | SM00072 | | WI | | 001-099 |
| 0070 | 22 | | GA | | 4-0 | 31-31-11 | D41443J | 1 | | | TB0181Z | 105 | BJ | | 115-199 |
| 0071 | 22 | | GA | | 3-8 | 31-31-01 | D41443J | 5 | | | TB0181Z | 108 | BJ | | 001-099 |
| 0071 | 22 | | GA | | 4-0 | 31-31-11 | D41443J | 5 | | | TB0181Z | 108 | BJ | | 115-199 |
| 0072 | 22 | | GA | | 3-8 | 31-31-01 | D41443J | 4 | | | TB0181Z | 106 | BJ | | 001-099 |
| 0072 | 22 | | GA | | 4-0 | 31-31-11 | D41443J | 4 | | | TB0181Z | 106 | BJ | | 115-199 |
| 0073 | 22 | | GA | | 0-7 | 31-31-01 | TB0181Z | 88 | BJ | | TB0181Z | 87 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | |
| 0073 | 22 | GA | | | 4-0 | 31-31-11 | D41443J | | 3 | | TB0181Z | 107 | BJ | | 115-199 |
| 0074 | 24 | GK | | | 3-1 | 31-31-01 | D41443J | | 8 | | D41519J | 31 | | | 001-099 |
| 0074 | 24 | GK | | | 4-0 | 31-31-11 | D41443J | | 8 | | D41519J | 31 | | | 115-199 |
| 0075 | 22 | GA | | | 3-10 | 31-31-61 | D41443J | | 2 | | D00011A | H03 | | | 001-099 |
| 0075 | 22 | GA | | | 4-0 | 31-31-11 | D41443J | | 2 | | D00011A | H03 | | | 115-199 |
| 0076 | 24 | GK | | | 2-8 | 31-31-01 | D00011A | A11 | | | TB0181Y | A104 | BJ | | 001-099 |
| 0076 | 22 | GA | | | 3-0 | 31-31-11 | D00011A | A11 | | | TB0181Y | A104 | BJ | | 115-199 |
| 0077 | 24 | GK | | | 2-7 | 31-31-01 | D41519J | | 28 | | D00011A | G15 | | | 001-099 |
| 0077 | 22 | GA | | | 3-0 | 31-31-11 | D41519J | | 28 | | D00011A | G15 | | | 115-199 |
| 0078 | 24 | GK | | | 2-4 | 31-31-01 | D41521J | | 14 | | D00011A | B11 | | | 001-099 |
| 0078 | 22 | GA | | | 3-0 | 31-31-11 | D41521J | | 14 | | D00011A | B11 | | | 115-199 |
| 0079 | 22 | GA | | | 2-4 | 31-31-01 | GD01955 | DC.. | 2 | | D00011A | J15 | | | 001-099 |
| 0079 | 22 | GA | | | 3-0 | 31-31-11 | GD01955 | DC.. | 2 | | D00011A | J15 | | | 115-199 |
| 0080 | 22 | GA | | | 2-4 | 31-31-01 | GD01955 | DC.. | 2 | | D00011A | K15 | | | 001-099 |
| 0080 | 22 | GA | | | 3-0 | 31-31-11 | GD01955 | DC.. | 2 | | D00011A | K15 | | | 115-199 |
| 0081 | 22 | GA | | | 2-5 | 31-31-01 | D41521J | | 20 | | SM00069 | | WI | | 001-099 |
| 0081 | 22 | GA | | | 3-0 | 31-31-11 | D41521J | | 20 | | TB0181Z | 105 | BJ | | 115-199 |
| 0082 | 22 | GA | | | 2-2 | 31-31-01 | D41521J | | 16 | | TB0181Z | 108 | BJ | | 001-099 |
| 0082 | 22 | GA | | | 3-0 | 31-31-11 | D41521J | | 16 | | TB0181Z | 107 | BJ | | 115-199 |
| 0083 | 22 | GA | | | 3-1 | 31-31-01 | D40678J | | 6 | | TB0181Z | 88 | BJ | | 001-099 |
| 0083 | 22 | GA | | | 3-0 | 31-31-11 | D41521J | | 17 | | TB0181Z | 106 | BJ | | 115-199 |
| 0084 | 24 | GK | | | 2-5 | 31-31-01 | D41521J | | 13 | | D41519J | 5 | | | 001-099 |
| 0084 | 22 | GA | | | 3-0 | 31-31-11 | D41521J | | 13 | | D41519J | 5 | | | 115-199 |
| 0085 | 22 | GA | | | 2-5 | 31-31-01 | D41519J | | 22 | | D00011C | 1 | | | 001-099 |
| 0085 | 22 | GA | | | 3-0 | 31-31-11 | D41519J | | 22 | | D00011C | 1 | | | 115-199 |
| 0086 | 22 | GA | | | 2-1 | 31-31-01 | GD01955 | AC.. | 2 | | D00011C | 7 | | | 001-099 |
| 0086 | 22 | GA | | | 3-0 | 31-31-11 | GD01955 | AC.. | 2 | | D00011C | 7 | | | 115-199 |
| 0087 | 24 | GK | | | 2-7 | 31-31-01 | D41519J | | 26 | | D00011D | G15 | | | 001-099 |
| 0087 | 24 | GK | | | 3-0 | 31-31-11 | D41519J | | 26 | | D00011D | G15 | | | 115-199 |
| 0088 | 24 | GK | | | 2-7 | 31-31-01 | D41519J | | 24 | | D00011D | H15 | | | 001-099 |
| 0088 | 24 | GK | | | 3-0 | 31-31-11 | D41519J | | 24 | | D00011D | H15 | | | 115-199 |
| 0089 | 22 | GA | | | 2-4 | 31-31-01 | GD01955 | DC.. | 2 | | D00011D | J15 | | | 001-099 |
| 0089 | 22 | GA | | | 3-0 | 31-31-11 | GD01955 | DC.. | 2 | | D00011D | J15 | | | 115-199 |
| 0090 | 22 | GA | | | 2-4 | 31-31-01 | GD01955 | DC.. | 2 | | D00011D | K15 | | | 001-099 |
| 0090 | 22 | GA | | | 3-0 | 31-31-11 | GD01955 | DC.. | 2 | | D00011D | K15 | | | 115-199 |
| 0091 | 20 | GA | | | 1-6 | 31-31-11 | D41519J | | | AJ | GD01953 | ST.. | 2 | | 115-199 |
| 0092 | 20 | GA | | | 1-6 | 31-31-01 | D41519J | | | AK | GD01952 | ST.. | 2 | | 001-099 |
| 0092 | 20 | GA | | | 1-6 | 31-31-11 | D41519J | | | AK | GD01953 | ST.. | 2 | | 115-199 |
| 0093 | 20 | GA | | | 1-6 | 31-31-11 | D41519J | | | AL | GD01953 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0095 | 20 | | GA | | 1-6 | 31-31-01 | D41521J | | | AN | GD01956 | ST.. | 2 | | 001-099 |
| 0095 | 20 | | GA | | 1-6 | 31-31-11 | D41521J | | | AN | GD01956 | ST.. | 2 | | 115-199 |
| 0096 | 20 | | GA | | 1-6 | 31-31-41 | D41443J | | | AP | GD01949 | ST.. | 2 | | 001-002 |
| 0096 | 20 | | GA | | 2-2 | 31-31-41 | D41443J | | | AP | GD01949 | ST.. | 2 | | 003-099 |
| 0096 | 20 | | GA | | 1-6 | 31-31-21 | D41443J | | | AP | GD01947 | ST.. | 2 | | 115-199 |
| 0097 | 20 | | GA | | 3-0 | 31-31-41 | D41309J | | | AQ | GD01949 | ST.. | 2 | | 001-099 |
| 0097 | 20 | | GA | | 3-0 | 31-31-21 | D41309J | | | AQ | GD01947 | ST.. | 2 | | 115-199 |
| 0098 | 20 | | GA | | 1-6 | 31-31-42 | D41443J | | | AR | GD01949 | ST.. | 2 | | 001-002 |
| 0098 | 20 | | GA | | 2-2 | 31-31-42 | D41443J | | | AR | GD01949 | ST.. | 2 | | 003-099 |
| 0098 | 20 | | GA | | 1-6 | 31-31-21 | D41309J | | | AR | GD01944 | ST.. | 2 | | 115-199 |
| 0099 | 20 | | GA | | 1-6 | 31-31-41 | D41309J | | | AS | GD01944 | ST.. | 2 | | 001-002 |
| 0099 | 20 | | GA | | 2-2 | 31-31-41 | D41309J | | | AS | GD03366 | ST.. | 2 | * | 003-099 |
| 0099 | 20 | | GA | | 1-6 | 31-31-21 | D41309J | | | AS | GD01944 | ST.. | 2 | | 115-199 |
| 0100 | 20 | | GA | | 2-4 | 31-31-41 | D41443J | | | AT | GD01947 | ST.. | X | | 001-099 |
| 0100 | 20 | | GA | | 1-6 | 31-31-21 | D41443J | | | AT | GD01947 | ST.. | 2 | | 115-199 |
| 0101 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | A09 | | D00749 | | 1 | | 001-010 |
| 0101 | 24 | | GK | | 3-1 | 31-31-65 | D00011D | | A09 | | D00749 | | 1 | | 011-099 |
| 0101 | 24 | | GK | | 3-0 | 31-31-21 | D00011D | | A09 | | D00749 | | 1 | | 115-199 |
| 0102 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | B09 | | D00749 | | 2 | | 001-010 |
| 0102 | 24 | | GK | | 3-1 | 31-31-65 | D00011D | | B09 | | D00749 | | 2 | | 011-099 |
| 0102 | 24 | | GK | | 3-0 | 31-31-21 | D00011D | | B09 | | D00749 | | 2 | | 115-199 |
| 0106 | 22 | | GA | | 3-6 | 34-53-11 | D00251B | | G05 | | D41525J | | 17 | | 001-002 |
| 0107 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | G09 | | D00749 | | 7 | VP | 001-008 |
| 0107 | 24 | | GK | | 4-0 | 31-31-65 | D00011D | | G09 | | D00749 | | 7 | VP | 009-010 |
| 0107 | 24 | | GK | | 3-1 | 31-31-65 | D00011D | | G09 | | D00749 | | 7 | VP | 011-099 |
| 0107 | 24 | | GK | | 3-0 | 31-31-21 | D00011D | | G09 | | D00749 | | 7 | | 115-199 |
| 0108 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | H09 | VP | D00749 | | 8 | | 001-002 |
| 0108 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | H09 | | D00749 | | 8 | VP | 003-008 |
| 0108 | 24 | | GK | | 4-0 | 31-31-65 | D00011D | | H09 | | D00749 | | 8 | VP | 009-010 |
| 0108 | 24 | | GK | | 3-1 | 31-31-65 | D00011D | | H09 | | D00749 | | 8 | VP | 011-099 |
| 0109 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | J09 | VP | D00749 | | 9 | | 001-002 |
| 0109 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | J09 | | D00749 | | 9 | VP | 003-008 |
| 0109 | 24 | | GK | | 4-0 | 31-31-65 | D00011D | | J09 | | D00749 | | 9 | VP | 009-010 |
| 0109 | 24 | | GK | | 3-1 | 31-31-65 | D00011D | | J09 | | D00749 | | 9 | VP | 011-099 |
| 0110 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | K09 | VP | D00749 | | 10 | | 001-002 |
| 0110 | 24 | | GK | | 2-5 | 31-31-65 | D00011D | | K09 | | D00749 | | 10 | VP | 003-008 |
| 0110 | 24 | | GK | | 4-0 | 31-31-65 | D00011D | | K09 | | D00749 | | 10 | VP | 009-010 |
| 0110 | 24 | | GK | | 3-1 | 31-31-65 | D00011D | | K09 | | D00749 | | 10 | VP | 011-099 |
| 0110 | 24 | | GK | | 4-0 | 34-53-11 | D00251A | | J05 | | D41525J | | 3 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|-------------------------------|----------|---------|------|--------|-------|---------|-------------|------|--------|-------------------------|
| | GA | CO | TY | | Equip | Term | Type | Splice | Equip | Term | | Type | Splice | |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | |
| 0111 | 24 | | GK | 2-5 | 31-31-65 | D00011D | A11 | | | D00749 | 11 | | | 001, 003, 005, 007, 009 |
| 0111 | 24 | | GK | 2-5 | 31-31-65 | D00011D | A11 | VP | | D00749 | 11 | | | 002 |
| 0111 | 24 | | GK | 2-5 | 31-31-65 | D00011D | A11 | | | D00749 | 11 | VP | | 004, 006, 008, 010 |
| 0111 | 24 | | GK | 3-1 | 31-31-65 | D00011D | A11 | | | D00749 | 11 | | | 011-099 |
| 0111 | 24 | | GK | 3-0 | 31-31-21 | D00011D | A11 | | | D00749 | 11 | VP | | 115-199 |
| 0112 | 24 | | GK | 2-5 | 31-31-65 | D00011D | B11 | VP | | D00749 | 12 | | | 001 |
| 0112 | 24 | | GK | 2-5 | 31-31-65 | D00011D | B11 | | | D00749 | 12 | | | 002-003, 006-007, 010 |
| 0112 | 24 | | GK | 2-5 | 31-31-65 | D00011D | B11 | | | D00749 | 12 | VP | | 004-005, 008-009 |
| 0112 | 24 | | GK | 3-1 | 31-31-65 | D00011D | B11 | | | D00749 | 12 | | | 011-099 |
| 0112 | 24 | | GK | 3-0 | 31-31-21 | D00011D | B11 | | | D00749 | 12 | | | 115-199 |
| 0113 | 24 | | GK | 2-5 | 31-31-65 | D00011D | C11 | VP | | D00749 | 13 | | | 001-002 |
| 0113 | 24 | | GK | 2-5 | 31-31-65 | D00011D | C11 | | | D00749 | 13 | VP | | 003, 008-010 |
| 0113 | 24 | | GK | 2-5 | 31-31-65 | D00011D | C11 | | | D00749 | 13 | | | 004-007 |
| 0113 | 24 | | GK | 3-1 | 31-31-65 | D00011D | C11 | | | D00749 | 13 | VP | | 011-099 |
| 0113 | 24 | | GK | 3-0 | 31-31-21 | D00011D | C11 | | | D00749 | 13 | VP | | 115-199 |
| 0114 | 24 | | GK | 2-5 | 31-31-65 | D00011D | D11 | | | D00749 | 14 | VP | | 001-007 |
| 0114 | 24 | | GK | 2-5 | 31-31-65 | D00011D | D11 | | | D00749 | 14 | | | 008-010 |
| 0114 | 24 | | GK | 3-1 | 31-31-65 | D00011D | D11 | | | D00749 | 14 | | | 011-099 |
| 0114 | 24 | | GK | 3-0 | 31-31-21 | D00011D | D11 | | | D00749 | 14 | VP | | 115-199 |
| 0115 | 24 | | GK | 2-5 | 31-31-65 | D00011D | E11 | | | D00749 | 15 | VP | | 001-010 |
| 0115 | 24 | | GK | 3-1 | 31-31-65 | D00011D | E11 | | | D00749 | 15 | VP | | 011-099 |
| 0115 | 24 | | GK | 3-0 | 31-31-21 | D00011D | E11 | | | D00749 | 15 | | | 115-199 |
| 0116 | 24 | | GK | 2-5 | 31-31-65 | D00011D | F11 | | | D00749 | 16 | VP | | 001-010 |
| 0116 | 24 | | GK | 3-1 | 31-31-65 | D00011D | F11 | | | D00749 | 16 | VP | | 011-099 |
| 0116 | 24 | | GK | 3-0 | 31-31-21 | D00011D | F11 | | | D00749 | 16 | VP | | 115-199 |
| 0117 | 24 | | GK | 2-5 | 31-31-65 | D00011D | G11 | | | D00749 | 17 | VP | | 001-010 |
| 0117 | 24 | | GK | 3-1 | 31-31-65 | D00011D | G11 | | | D00749 | 17 | VP | | 011-099 |
| 0117 | 24 | | GK | 3-0 | 31-31-21 | D00011D | G11 | | | D00749 | 17 | VP | | 115-199 |
| 0118 | 24 | | GK | 2-5 | 31-31-65 | D00011D | H11 | | | D00749 | 18 | VP | | 001-010 |
| 0118 | 24 | | GK | 3-1 | 31-31-65 | D00011D | H11 | | | D00749 | 18 | VP | | 011-099 |
| 0118 | 24 | | GK | 3-0 | 31-31-21 | D00011D | H11 | | | D00749 | 18 | | | 115-199 |
| 0119 | 24 | | GK | 2-5 | 31-31-65 | D00011D | K11 | | | D00749 | 19 | | | 001-010 |
| 0119 | 24 | | GK | 3-1 | 31-31-65 | D00011D | K11 | | | D00749 | 19 | | | 011-099 |
| 0119 | 24 | | GK | 3-0 | 31-31-21 | D00011D | K11 | | | D00749 | 19 | | | 115-199 |
| 0120 | 22 | | GA | 3-10 | 31-31-61 | D41443J | 17 | | | D00011A | J03 | | | 001-099 |
| 0120 | 22 | | GA | 4-0 | 31-31-21 | D41443J | 17 | | | D00011A | J03 | | | 115-199 |
| 0121 | 22 | | GA | 3-2 | 34-22-17 | D42019J | 1 | | | SM00002 | | WI | | 001, 003-099 |
| 0121 | 22 | | GA | 3-2 | 34-22-17 | D42019J | 1 | | | SM00002 | | 9 | | 002 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | |
| 0121 | 22 | | GA | | 3-0 | 34-22-17 | D42019J | | 1 | | SM00002 | | WI | | 115-199 |
| 0122 | 24 | | GK | | 2-9 | 31-31-61 | D41443J | | 9 | | SM00002 | | WI | | 001, 003-099 |
| 0122 | 24 | | GK | | 2-9 | 31-31-61 | D41443J | | 9 | | SM00002 | | 9 | | 002 |
| 0122 | 22 | | GA | | 2-0 | 31-31-21 | D41443J | | 9 | | SM00002 | | WI | | 115-199 |
| 0123 | 24 | | GK | | 2-4 | 31-31-62 | D00011A | | F03 | | D41307J | 34 | | | 001-099 |
| 0123 | 22 | | GA | | 4-0 | 31-31-21 | D00011A | | F03 | | SM00002 | | WI | | 115-199 |
| 0124 | 22 | | GA | | 3-2 | 34-12-61 | D42019J | | 13 | | SM00003 | | WI | | 001-099 |
| 0124 | 22 | | GA | | 3-0 | 34-12-61 | D42019J | | 13 | | SM00003 | | WI | | 115-199 |
| 0126 | 24 | | GK | | 3-7 | 31-31-62 | D00011D | | H01 | | D41361J | 40 | | | 001-099 |
| 0126 | 22 | | GA | | 4-0 | 31-31-21 | D00011A | | G01 | | SM00003 | | WI | | 115-199 |
| 0127 | 20 | | GA | | 1-6 | 31-31-22 | D41309J | | | AU | GD01947 | ST.. | 2 | | 115-199 |
| 0128 | 20 | | GA | | 1-6 | 31-31-22 | D41403J | | | AV | GD01953 | ST.. | 2 | | 115-199 |
| 0129 | 24 | | GK | | 4-0 | 34-53-11 | D00251A | | G07 | | D41525J | 4 | | | 115-199 |
| 0130 | 24 | | GK | | 4-0 | 34-53-11 | D00251A | | F07 | | D41525J | 11 | | | 115-199 |
| 0131 | 20 | | GA | | 1-6 | 31-31-51 | D41956J | | | BA | GD01956 | ST.. | 2 | | 001-099 |
| 0131 | 20 | | GA | | 1-6 | 31-31-31 | D41956J | | | BA | GD01956 | ST.. | 2 | | 115-199 |
| 0132 | 20 | | GA | | 1-6 | 31-31-51 | D41956J | | | BB | GD01956 | ST.. | 2 | | 001-099 |
| 0132 | 20 | | GA | | 1-6 | 31-31-31 | D41956J | | | BB | GD01956 | ST.. | 2 | | 115-199 |
| 0133 | 20 | | GA | | 1-6 | 31-31-51 | D41956J | | | BC | GD01956 | ST.. | 2 | | 001-099 |
| 0133 | 20 | | GA | | 1-6 | 31-31-31 | D41956J | | | BC | GD01956 | ST.. | 2 | | 115-199 |
| 0134 | 22 | | GA | | 3-0 | 31-31-32 | D00011B | | B11 | | GD01955 | AC.. | 2 | | 115-199 |
| 0135 | 22 | | GA | | 3-0 | 31-31-32 | D00011E | | B08 | | GD01955 | AC.. | 2 | | 115-199 |
| 0136 | 22 | | GA | | 3-0 | 31-31-32 | D00011B | | C02 | | GD01955 | AC.. | 2 | | 115-199 |
| 0137 | 24 | | GK | | 3-7 | 34-53-11 | D00251A | | J05 | | D41525J | 15 | | | 001-099 |
| 0138 | 24 | | GK | | 3-2 | 31-31-51 | D00011B | | H04 | | TB0181Z | 87 | BJ | | 001-099 |
| 0138 | 24 | | GK | | 5-0 | 31-31-32 | D00011B | | H04 | | D41309J | 12 | | | 115-199 |
| 0139 | 24 | | GK | | 3-10 | 31-31-61 | D00011D | | A03 | | D41443J | 21 | | | 001-099 |
| 0139 | 24 | | GK | | 4-0 | 31-31-31 | D00011D | | A03 | | D41443J | 21 | | | 115-199 |
| 0140 | 24 | | GK | | 3-10 | 31-31-61 | D00011D | | B03 | | D41443J | 22 | | | 001-099 |
| 0140 | 24 | | GK | | 4-0 | 31-31-31 | D00011D | | B03 | | D41443J | 22 | | | 115-199 |
| 0141 | 24 | | GK | | 3-10 | 31-31-61 | D00011A | | K01 | | D41443J | 23 | | | 001-099 |
| 0141 | 24 | | GK | | 4-0 | 31-31-31 | D00011A | | K01 | | D41443J | 23 | | | 115-199 |
| 0142 | 24 | | GK | | 3-10 | 31-31-61 | D00011A | | A03 | | D41443J | 24 | | | 001-099 |
| 0142 | 24 | | GK | | 4-0 | 31-31-31 | D00011A | | A03 | | D41443J | 24 | | | 115-199 |
| 0143 | 24 | | GK | | 4-2 | 31-31-61 | D00011A | | A01 | | D41309J | 18 | | | 001-099 |
| 0143 | 24 | | GK | | 5-0 | 31-31-32 | D00011A | | A01 | | D41309J | 18 | | | 115-199 |
| 0144 | 24 | | GK | | 4-2 | 31-31-61 | D00011A | | C01 | | D41309J | 21 | | | 001-099 |
| 0144 | 24 | | GK | | 5-0 | 31-31-32 | D00011A | | C01 | | D41309J | 21 | | | 115-199 |
| 0145 | 24 | | GK | | 3-7 | 31-31-61 | D00011D | | B01 | | D41361J | 14 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--------------------------------------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | |
| 0145 | 24 | GK | | | 4-0 | 31-31-32 | D00011D | B01 | | | D41361J | 14 | | | 115-199 |
| 0146 | 24 | GK | | | 3-7 | 31-31-61 | D00011D | D01 | | | D41361J | 15 | | | 001-099 |
| 0148 | 24 | GK | | | 4-2 | 31-31-61 | D00011A | E01 | | | D41309J | 19 | | | 001-099 |
| 0148 | 24 | GK | | | 5-0 | 31-31-31 | D00011D | H01 | | | D41309J | 19 | | | 115-199 |
| 0149 | 24 | GK | | | 3-10 | 31-31-63 | D00011A | F01 | | | D41443J | 41 | | | 001-099 |
| 0149 | 24 | GK | | | 5-0 | 31-31-31 | D00011A | F01 | | | D41309J | 20 | | | 115-199 |
| 0150 | 20 | GA | | | 1-6 | 31-31-13 | D41523J | | | AY | GD01942 | ST.. | 2 | | 115-199 |
| 0151 | 20 | GA | | | 1-6 | 31-31-13 | D41523J | | | AZ | GD01942 | ST.. | 2 | | 115-199 |
| 0152 | 22 | GA | | | 3-0 | 31-31-13 | D00777A | A05 | | | GD01955 | ST.. | 2 | | 115-199 |
| 0153 | 22 | GA | | | 3-0 | 31-31-13 | D00777A | K05 | | | GD01955 | DC.. | 2 | | 115-199 |
| 0154 | 22 | GA | | | 3-0 | 31-31-13 | D00777C | 4 | | | GD01955 | AC.. | 2 | | 115-199 |
| 0155 | 22 | GA | | | 3-0 | 31-31-13 | D00777C | 1 | | | TB0181Z | 106 | BJ | | 115-199 |
| 0157 | 22 | GA | | | 4-0 | 31-31-11 | D41443J | 44 | | | TB0181Z | 105 | BJ | | 115-199 |
| 0158 | 22 | GA | | | 3-0 | 31-31-11 | TB0181Z | 109 | BJ | | TB0181Z | 105 | BJ | | 115-199 |
| 0159 | 22 | GA | | | 2-5 | 34-25-11 | D41309J | 45 | | | SM00002 | | WI | | 001, 003-099 |
| 0159 | 22 | GA | | | 2-0 | 34-25-11 | D41309J | 45 | | | SM00002 | | WI | | 115-199 |
| 0160 | 20 | GA | | | 1-6 | SPARE | D41361J | | | BD | GD01947 | ST.. | 2 | | 115-199 |
| 0161 | 20 | GA | | | 1-6 | 31-31-22 | D41307J | | | BE | GD01956 | ST.. | 2 | | 115-199 |
| 0162 | 20 | GA | | | 1-6 | 31-31-22 | D41307J | | | BF | GD01956 | ST.. | 2 | | 115-199 |
| 0163 | 20 | GA | | | 1-6 | 31-31-22 | D41361J | | | BG | GD01947 | ST.. | 2 | | 115-199 |
| 0164 | 20 | GA | | | 1-6 | 31-31-22 | D41361J | | | BH | GD01947 | ST.. | 2 | | 115-199 |
| 0165 | 20 | GA | | | 1-6 | 31-31-22 | D41361J | | | BI | GD01947 | ST.. | 2 | | 115-199 |
| 0166 | 20 | GA | | | 1-6 | 31-31-22 | D41403J | | | BJ | GD01952 | ST.. | 2 | | 115-199 |
| 0167 | 20 | GA | | | 1-6 | 31-31-22 | D41403J | | | BK | GD01952 | ST.. | 2 | | 115-199 |
| 0168 | 20 | GA | | | 1-6 | 31-31-22 | D41443J | | | BL | GD01947 | ST.. | 2 | | 115-199 |
| 0169 | 20 | GA | | | 1-6 | 31-31-42 | D41307J | | | GR | GD01955 | ST.. | 2 | | 010-099 |
| 0169 | 20 | GA | | | 1-6 | 31-31-22 | D42019J | | | BM | GD01942 | ST.. | 2 | | 115-199 |
| 0170 | 20 | GA | | | 1-6 | 31-31-22 | D41307J | | | BN | GD01956 | ST.. | 2 | | 115-199 |
| 0171 | 20 | GA | | | 1-6 | 31-31-22 | D41361J | | | BP | GD01947 | ST.. | 2 | | 115-199 |
| 0172 | 20 | GA | | | 1-6 | 31-31-22 | D41403J | | | BQ | GD01952 | ST.. | 2 | | 115-199 |
| 0174 | 24 | GK | | | 3-3 | 31-31-01 | D41443J | 54 | | | TB0181Y | A104 | BJ | | 001-099 |
| 0174 | 24 | GK | | | 4-0 | 31-31-11 | D41443J | 54 | | | TB0181Y | A104 | BJ | | 115-199 |
| 0175 | 24 | GK | | | 2-0 | 31-31-01 | D41519J | 6 | | | TB0181Y | A104 | BJ | | 001-099 |
| 0175 | 24 | GK | | | 3-0 | 31-31-11 | D41519J | 6 | | | TB0181Y | A104 | BJ | | 115-199 |
| 0176 | 22 | GA | | | 3-0 | 31-31-31 | D00011B | B08 | | | GD01955 | AC.. | 2 | | 115-199 |
| 0177 | 20 | GA | | | 1-6 | 31-31-42 | D41309J | | | AU | GD01944 | ST.. | 2 | | 001-099 |
| 0177 | 24 | GK | | | 4-0 | 31-31-31 | D41443J | 34 | | | D00011D | D05 | | | 115-199 |
| 0178 | 24 | GK | | | 4-0 | 31-31-31 | D41443J | 36 | | | D00011D | E05 | | | 115-199 |
| 0179 | 22 | GA | | | 3-0 | 31-31-31 | D00011A | C03 | | | D41307J | 48 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0180 | 24 | | GK | | 4-0 | 31-31-62 | | D41309J | | 2 | | SM00069 | | WI | | 001-099 |
| 0181 | 24 | | GK | | 4-0 | 31-31-31 | | D41443J | | 35 | | TB0181Z | 105 | BJ | | 115-199 |
| 0182 | 24 | | GK | | 5-0 | 31-31-31 | | D42019J | | 4 | | D00011A | B05 | | | 115-199 |
| 0183 | 24 | | GK | | 5-0 | 31-31-31 | | D42019J | | 2 | | D00011D | C05 | | | 115-199 |
| 0184 | 24 | | GK | | 5-0 | 31-31-31 | | D42019J | | 3 | | D00011A | C05 | | | 115-199 |
| 0185 | 24 | | GK | | 3-0 | 31-31-32 | | D41307J | | 19 | | D00011A | G03 | | | 115-199 |
| 0186 | 24 | | GK | | 4-0 | 31-31-32 | | D41361J | | 31 | | D00011D | H03 | | | 115-199 |
| 0187 | 24 | | GK | | 3-7 | 31-31-62 | | D00011A | H01 | | | D41361J | 41 | | | 001-099 |
| 0187 | 24 | | GK | | 4-0 | 31-31-31 | | D41443J | | 48 | | D00011A | J01 | | | 115-199 |
| 0188 | 24 | | GK | | 3-0 | 31-31-31 | | D00011A | E01 | | | TB0181Y | C104 | BJ | | 115-199 |
| 0189 | 24 | | GK | | 4-4 | 31-31-61 | | D00011D | G01 | | | SM00003 | | WI | | 001-099 |
| 0189 | 24 | | GK | | 3-0 | 31-31-31 | | D00011D | G01 | | | TB0181Y | C104 | BJ | | 115-199 |
| 0190 | 24 | | GK | | 4-0 | 31-31-31 | | D41443J | | 50 | | TB0181Y | C104 | BJ | | 115-199 |
| 0191 | 24 | | GK | | 3-7 | 31-31-62 | | D41361J | | 42 | | D00011D | J01 | | | 001-099 |
| 0191 | 24 | | GK | | 4-0 | 31-31-31 | | D41443J | | 49 | | D00011D | K01 | | | 115-199 |
| 0192 | 24 | | GK | | 4-11 | 31-31-61 | | D00011D | E01 | | | D42019J | 27 | | | 001-099 |
| 0192 | 24 | | GK | | 4-0 | 31-31-32 | | D41361J | | 32 | | D00011D | E01 | | | 115-199 |
| 0193 | 24 | | GK | | 2-4 | 31-31-62 | | D41307J | | 17 | | D00011D | K01 | | | 001-099 |
| 0193 | 24 | | GK | | 4-0 | 31-31-32 | | D41361J | | 33 | | D00011D | J01 | | | 115-199 |
| 0194 | 24 | | GK | | 2-4 | 31-31-62 | | D41307J | | 16 | | D00011A | J01 | | | 001-099 |
| 0194 | 24 | | GK | | 4-0 | 31-31-32 | | D41361J | | 34 | | D00011D | A01 | | | 115-199 |
| 0195 | 24 | | GK | | 4-0 | 31-31-32 | | D41361J | | 35 | | D00011D | C01 | | | 115-199 |
| 0196 | 20 | | GA | | 1-6 | 31-31-22 | | D41309J | | | BU | GD01944 | ST.. | 2 | | 115-199 |
| 0197 | 20 | | GA | | 1-6 | 31-31-22 | | D41361J | | | BV | GD01947 | ST.. | 2 | | 115-199 |
| 0198 | 24 | | GK | | 3-7 | 34-53-11 | | D00251A | | K05 | | D41525J | 11 | | | 001-099 |
| 0199 | 24 | | GK | | 3-7 | 34-53-11 | | D00251A | | B03 | | D41525J | 12 | | | 001-099 |
| 0200 | 22 | | GA | | 4-0 | 31-31-32 | | D41443J | | 53 | | D00011A | H05 | | | 115-199 |
| 0201 | 22 | | GA | | 3-0 | 31-31-32 | | D41307J | | 12 | | D00011A | D05 | | | 115-199 |
| 0202 | 22 | | GA | | 4-0 | 31-31-32 | | D41361J | | 37 | | D00011A | E05 | | | 115-199 |
| 0203 | 22 | | GA | | 3-0 | 31-31-32 | | D41307J | | 13 | | D00011D | F05 | | | 115-199 |
| 0204 | 22 | | GA | | 4-0 | 31-31-32 | | D41361J | | 38 | | D00011D | G05 | | | 115-199 |
| 0205 | 24 | | GK | | 2-4 | 31-31-62 | | D00011D | | K03 | | D41307J | 48 | | | 001-099 |
| 0205 | 22 | | GA | | 3-0 | 31-31-32 | | D41307J | | 10 | | D00011D | H05 | | | 115-199 |
| 0206 | 24 | | GK | | 3-7 | 31-31-62 | | D00011A | | K03 | | D41361J | 43 | | | 001-099 |
| 0206 | 22 | | GA | | 4-0 | 31-31-32 | | D41361J | | 36 | | D00011D | J05 | | | 115-199 |
| 0207 | 24 | | GK | | 4-0 | 31-31-32 | | D41361J | | 39 | | D00011D | C03 | | | 115-199 |
| 0208 | 24 | | GK | | 4-4 | 31-31-61 | | D00011A | | B03 | | SM00002 | | WI | | 001, 003-099 |
| 0208 | 24 | | GK | | 4-4 | 31-31-61 | | D00011A | | B03 | | SM00002 | | 9 | | 002 |
| 0208 | 24 | | GK | | 3-0 | 31-31-32 | | D41307J | | 14 | | D00011A | B03 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | |
| 0209 | 22 | GA | | | 3-0 | 31-31-32 | D41307J | | 18 | | D00011A | F05 | | | 115-199 |
| 0210 | 22 | GA | | | 4-0 | 31-31-32 | D41361J | | 43 | | D00011A | G05 | | | 115-199 |
| 0211 | 24 | GK | | | 2-4 | 31-31-62 | D41307J | | 19 | | D00011A | E05 | | | 001-099 |
| 0211 | 22 | GA | | | 5-0 | 31-31-31 | D42019J | | 25 | | D00011A | K05 | | | 115-199 |
| 0212 | 24 | GK | | | 2-4 | 31-31-62 | D41307J | | 14 | | D00011A | F05 | | | 001-099 |
| 0212 | 22 | GA | | | 5-0 | 31-31-31 | D42019J | | 30 | | D00011A | A07 | | | 115-199 |
| 0213 | 22 | GA | | | 5-0 | 31-31-31 | D42019J | | 31 | | D00011A | J05 | | | 115-199 |
| 0214 | 22 | GA | | | 5-0 | 31-31-31 | D42019J | | 11 | | D00011D | K05 | | | 115-199 |
| 0215 | 24 | GK | | | 3-7 | 31-31-62 | D41361J | | 31 | | D00011D | F05 | | | 001-099 |
| 0215 | 22 | GA | | | 5-0 | 31-31-31 | D42019J | | 12 | | D00011D | A07 | | | 115-199 |
| 0216 | 24 | GK | | | 3-7 | 31-31-62 | D41361J | | 39 | | D00011D | G05 | | | 001-099 |
| 0216 | 22 | GA | | | 5-0 | 31-31-31 | D42019J | | 24 | | D00011D | B07 | | | 115-199 |
| 0217 | 24 | GK | | | 3-0 | 31-31-32 | D41307J | | 15 | | TB0181B | A093 | 2 | | 115-199 |
| 0218 | 24 | GK | | | 3-0 | 31-31-32 | D41307J | | 16 | | TB0181B | A094 | 2 | | 115-199 |
| 0219 | 24 | GK | | | 3-0 | 31-31-32 | D41307J | | 17 | | TB0181B | A095 | 2 | | 115-199 |
| 0220 | 24 | GK | | | 3-0 | 31-31-32 | D00011D | A05 | | | TB0181B | A093 | 2 | | 115-199 |
| 0221 | 24 | GK | | | 4-2 | 31-31-62 | D00011D | J05 | | | D41309J | 3 | | | 001-099 |
| 0221 | 24 | GK | | | 3-0 | 31-31-32 | D00011A | A05 | | | TB0181B | A094 | 2 | | 115-199 |
| 0222 | 24 | GK | | | 3-5 | 31-31-62 | D00011E | J02 | | | D41361J | 32 | | | 001-099 |
| 0222 | 24 | GK | | | 3-0 | 31-31-32 | D00011D | B05 | | | TB0181B | A095 | 2 | | 115-199 |
| 0223 | 22 | GA | | | 3-0 | 31-31-32 | TB0181B | C093 | 2 | | TB0181Z | 109 | BJ | | 115-199 |
| 0224 | 22 | GA | | | 3-0 | 31-31-32 | TB0181B | C094 | 2 | | TB0181Z | 109 | BJ | | 115-199 |
| 0225 | 22 | GA | | | 3-0 | 31-31-32 | TB0181B | C095 | 2 | | TB0181Z | 109 | BJ | | 115-199 |
| 0226 | 22 | GA | | | 5-0 | 31-31-31 | D42019J | 10 | | | TB0181Z | 109 | BJ | | 115-199 |
| 0227 | 24 | GK | | | 4-0 | 31-31-32 | D41361J | 40 | | | TB0181B | A096 | 2 | | 115-199 |
| 0228 | 24 | GK | | | 4-0 | 31-31-32 | D41361J | 41 | | | TB0181B | A097 | 2 | | 115-199 |
| 0229 | 24 | GK | | | 4-0 | 31-31-32 | D41361J | 42 | | | TB0181B | A098 | 2 | | 115-199 |
| 0230 | 24 | GK | | | 3-5 | 31-31-62 | D00011E | K02 | | | D41361J | 33 | | | 001-099 |
| 0230 | 24 | GK | | | 3-0 | 31-31-32 | D00011D | D03 | | | TB0181B | A096 | 2 | | 115-199 |
| 0231 | 24 | GK | | | 3-0 | 31-31-32 | D00011D | J03 | | | TB0181B | A097 | 2 | | 115-199 |
| 0232 | 24 | GK | | | 3-0 | 31-31-32 | D00011A | K03 | | | TB0181B | A098 | 2 | | 115-199 |
| 0233 | 22 | GA | | | 3-0 | 31-31-32 | TB0181B | C096 | 2 | | TB0181Z | 109 | BJ | | 115-199 |
| 0234 | 22 | GA | | | 3-0 | 31-31-32 | TB0181B | C097 | 2 | | TB0181Z | 109 | BJ | | 115-199 |
| 0235 | 22 | GA | | | 3-0 | 31-31-32 | TB0181B | C098 | 2 | | TB0181Z | 109 | BJ | | 115-199 |
| 0236 | 20 | GA | | | 1-6 | 31-31-41 | D43315J | | | DW | GD01944 | ST.. | 2 | | 010-099 |
| 0237 | 24 | GK | | | 4-8 | 32-61-12 | D42071J | 11 | | | D41307J | 10 | | | 001-099 |
| 0237 | 22 | GA | | | 5-0 | 32-61-12 | D42071J | 11 | | | D41307J | 27 | | | 115-199 |
| 0239 | 22 | GA | | | 4-8 | 32-61-12 | D42071J | 10 | | | D41307J | 12 | | | 001-099 |
| 0239 | 22 | GA | | | 5-0 | 32-61-12 | D42071J | 10 | | | D41307J | 29 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W1433 | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0240 | 24 | | GK | | 4-0 | 31-31-32 | D41443J | | 38 | | D00011D | | C07 | | | 115-199 |
| 0241 | 24 | | GK | | 4-0 | 31-31-32 | D41443J | | 42 | | D00011D | | D07 | | | 115-199 |
| 0242 | 24 | | GK | | 4-8 | 32-61-12 | D42071J | | 2 | | D41307J | | 8 | | | 001-099 |
| 0242 | 24 | | GK | | 5-0 | 32-61-12 | D42071J | | 2 | | D41307J | | 30 | | | 115-199 |
| 0243 | 22 | | GA | | 4-8 | 32-61-12 | D42071J | | 1 | | D41307J | | 11 | | | 001-099 |
| 0243 | 22 | | GA | | 5-0 | 32-61-12 | D42071J | | 1 | | D41307J | | 11 | | | 115-199 |
| 0256 | 22 | | GA | | 2-7 | 31-31-52 | D41113J | | 4 | | GD01954 | AC.. | 2 | | | 001-099 |
| 0257 | 24 | | GK | | 2-3 | 31-31-52 | D41113J | | 3 | | D00011B | | C04 | | | 001-099 |
| 0258 | 24 | | GK | | 3-1 | 31-31-52 | D41113J | | 1 | | TB0181Z | | 87 | BJ | | 001-099 |
| 0259 | 24 | | GK | | 3-1 | 31-31-52 | D41113J | | 2 | | TB0181Z | | 87 | BJ | | 001-099 |
| 0260 | 24 | | GK | | 2-3 | 31-31-52 | D41113J | | 5 | | D00011B | | C07 | | | 001-099 |
| 0261 | 22 | | GA | | 2-7 | 31-31-52 | D41113J | | 6 | | GD01954 | AC.. | 2 | | | 001-099 |
| 0262 | 22 | | GA | | 2-3 | 31-31-52 | D00011B | | C05 | | GD01955 | AC.. | 2 | | | 001-099 |
| 0263 | 24 | | GK | | 3-2 | 31-31-52 | D00011B | | C06 | | TB0181Z | | 87 | BJ | | 001-099 |
| 0264 | 24 | | GK | | 3-2 | 31-31-52 | D00011B | | C09 | | TB0181Z | | 87 | BJ | | 001-099 |
| 0265 | 22 | | GA | | 2-3 | 31-31-52 | D00011B | | C08 | | GD01955 | AC.. | 2 | | | 001-099 |
| 0266 | 22 | | GA | | 2-7 | 31-31-52 | D41115J | | 4 | | GD01954 | AC.. | 2 | | | 001-099 |
| 0267 | 24 | | GK | | 2-3 | 31-31-52 | D41115J | | 3 | | D00011E | | C04 | | | 001-099 |
| 0268 | 24 | | GK | | 3-1 | 31-31-52 | D41115J | | 1 | | TB0181Z | | 88 | BJ | | 001-099 |
| 0269 | 24 | | GK | | 3-1 | 31-31-52 | D41115J | | 2 | | TB0181Z | | 88 | BJ | | 001-099 |
| 0270 | 24 | | GK | | 2-3 | 31-31-52 | D41115J | | 5 | | D00011E | | C07 | | | 001-099 |
| 0271 | 22 | | GA | | 2-7 | 31-31-52 | D41115J | | 6 | | GD01954 | AC.. | 2 | | | 001-099 |
| 0272 | 22 | | GA | | 2-3 | 31-31-52 | D00011E | | C08 | | GD01955 | AC.. | 2 | | | 001-099 |
| 0273 | 24 | | GK | | 3-2 | 31-31-52 | D00011E | | C09 | | TB0181Z | | 88 | BJ | | 001-099 |
| 0274 | 24 | | GK | | 3-2 | 31-31-52 | D00011E | | C06 | | TB0181Z | | 88 | BJ | | 001-099 |
| 0275 | 22 | | GA | | 2-3 | 31-31-52 | D00011E | | C05 | | GD01955 | AC.. | 2 | | | 001-099 |
| 0277 | 24 | | GK | | 3-10 | 31-31-61 | D00011A | | B01 | | D41443J | | 33 | | | 001-099 |
| 0281 | 24 | | GK | | 3-9 | 31-31-61 | D41443J | | 37 | | SM00069 | | | WI | | 001-099 |
| 0282 | 24 | | GK | | 2-4 | 31-31-62 | D00011A | | G01 | | D41307J | | 15 | | | 001-099 |
| 0283 | 24 | | GK | | 3-10 | 31-31-63 | D00011D | | F01 | | D41443J | | 40 | | | 001-099 |
| 0293 | 24 | | GK | | 3-10 | 31-31-62 | D00011D | | J03 | | D41443J | | 43 | | | 001-099 |
| 0294 | 24 | | GK | | 3-10 | 31-31-62 | D00011A | | G07 | | D41443J | | 48 | | | 001-099 |
| 0295 | 24 | | GK | | 3-7 | 31-31-62 | D00011D | | G03 | | D41361J | | 4 | | | 001-099 |
| 0296 | 24 | | GK | | 3-5 | 31-31-62 | D00011B | | J02 | | D41361J | | 35 | | | 001-099 |
| 0297 | 22 | | GA | | 2-5 | 31-31-63 | D41361J | | 49 | | SM00072 | | | WI | | 001-099 |
| 0298 | 22 | | GA | | 3-7 | 31-31-63 | D00011D | | C03 | | D41361J | | 50 | | | 001-099 |
| 0299 | 22 | | GA | | 1-10 | 31-31-63 | D41361J | | 51 | | GD01949 | DC.. | 2 | | | 001-099 |
| 0300 | 24 | | GK | | 3-7 | 34-53-11 | D00251A | | G07 | | D41525J | | 7 | | | 001-099 |
| 0333 | 24 | | GK | | 2-9 | 31-31-51 | D41145J | | 1 | | TB0181Z | | 87 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | |
| 0334 | 24 | GK | | | 2-9 | 31-31-51 | D41145J | | 4 | | TB0181Z | 87 | BJ | | 001-099 |
| 0335 | 24 | GK | | | 2-9 | 31-31-51 | D41145J | | 7 | | TB0181Z | 88 | BJ | | 001-099 |
| 0336 | 22 | GA | | | 2-3 | 31-31-51 | D00011E | | A05 | | GD01955 | AC.. | 2 | | 001-099 |
| 0337 | 22 | GA | | | 2-3 | 31-31-51 | D00011E | | A08 | | GD01955 | AC.. | 2 | | 001-099 |
| 0338 | 22 | GA | | | 2-3 | 31-31-51 | D00011B | | A08 | | GD01955 | AC.. | 2 | | 001-099 |
| 0339 | 22 | GA | | | 1-6 | 34-45-02 | D41307J | | | BY | GD01951 | ST.. | 2 | | 001-002 |
| 0339 | 22 | GA | | | 2-7 | 34-45-02 | D41307J | | | BY | GD01952 | ST.. | 2 | | 003-099 |
| 0339 | 22 | GA | | | 3-0 | 34-45-02 | D41307J | | | BY | GD01951 | ST.. | 2 | | 115-199 |
| 0340 | 22 | GA | | | 1-6 | 34-45-02 | D41307J | | | BZ | GD01951 | ST.. | 2 | | 001-002 |
| 0340 | 22 | GA | | | 2-7 | 34-45-02 | D41307J | | | BZ | GD01952 | ST.. | 2 | | 003-099 |
| 0340 | 22 | GA | | | 3-0 | 34-45-02 | D41307J | | | BZ | GD01951 | ST.. | 2 | | 115-199 |
| 0341 | 22 | GA | | | 1-6 | 34-45-01 | D41307J | | | CZ | GD01951 | ST.. | 2 | | 001-002 |
| 0341 | 22 | GA | | | 2-7 | 34-45-01 | D41307J | | | CZ | GD01952 | ST.. | 2 | | 003-099 |
| 0341 | 22 | GA | | | 3-0 | 34-45-01 | D41307J | | | CZ | GD01951 | ST.. | 2 | | 115-199 |
| 0342 | 22 | GA | | | 2-3 | 34-53-11 | D00251B | | E06 | | D42019J | | 5 | | 001-099 |
| 0344 | 24 | GK | | | 2-4 | 34-53-12 | D00251B | | J05 | | TB0181Y | A003 | BJ | | 001-099 |
| 0345 | 22 | GA | | | 2-9 | 31-31-42 | D41443J | | 38 | | SM00081 | | WI | | 001-099 |
| 0346 | 22 | GA | | | 3-3 | 31-31-42 | D41443J | | 55 | | TB0181A | C090 | 2 | | 001-099 |
| 0347 | 22 | GA | | | 2-6 | 31-31-42 | TB0181A | | A090 | 2 | SM00069 | | WI | | 001-099 |
| 0348 | 24 | GK | | | 2-5 | 31-31-61 | D41309J | | 20 | | SM00081 | | WI | | 001-099 |
| 0349 | 24 | GK | | | 4-4 | 31-31-61 | D00011A | | D01 | | SM00081 | | WI | | 001-099 |
| 0350 | 24 | GK | | | 3-5 | 31-31-62 | D41361J | | 34 | | D00011B | K01 | | | 001-099 |
| 0383 | 24 | GK | | | 4-2 | 31-31-62 | D00011A | | H05 | | D41309J | 1 | | | 001-099 |
| 0394 | 24 | GK | | | 4-4 | 31-31-65 | D00011A | | F07 | VP | SM00072 | | WI | | 002-009 |
| 0395 | 22 | GA | | | 2-3 | 31-31-65 | D00011E | | J06 | VP | GD01956 | ST.. | 2 | | 001 |
| 0397 | 24 | GK | | | 2-8 | 31-31-62 | D00011A | | G05 | | D41403J | 16 | | | 001-099 |
| 0398 | 24 | GK | | | 2-8 | 31-31-62 | D00011D | | H05 | | D41403J | 17 | | | 001-099 |
| 0404 | 20 | GA | | | 1-6 | 31-31-42 | D41403J | | | DB | GD01952 | ST.. | 2 | | 001-099 |
| 0405 | 20 | GA | | | 1-6 | 31-31-42 | D41361J | | | DA | GD01949 | ST.. | 2 | | 001-099 |
| 0406 | 20 | GA | | | 1-6 | 31-31-42 | D42019J | | | DC | GD01944 | ST.. | 2 | | 001-099 |
| 0407 | 20 | GA | | | 1-6 | 31-31-42 | D41403J | | | DD | GD01952 | ST.. | 2 | | 001-099 |
| 0408 | 20 | GA | | | 1-6 | 31-31-43 | D41361J | | | DE | GD01949 | ST.. | 2 | | 001-099 |
| 0409 | 20 | GA | | | 1-6 | 31-31-43 | D41361J | | | DF | GD01949 | ST.. | 2 | | 001-099 |
| 0410 | 20 | GA | | | 1-6 | 31-31-43 | D41361J | | | DG | GD01949 | ST.. | 2 | | 001-099 |
| 0411 | 20 | GA | | | 1-6 | 31-31-43 | D41361J | | | DH | GD01949 | ST.. | 2 | | 001-009 |
| 0412 | 20 | GA | | | 1-6 | 31-31-43 | D41403J | | | DI | GD01952 | ST.. | 2 | | 001-099 |
| 0413 | 20 | GA | | | 1-6 | 31-31-43 | D41361J | | | DJ | GD01949 | ST.. | 2 | | 001-099 |
| 0414 | 20 | GA | | | 1-6 | 31-31-43 | D41307J | | | DK | GD01956 | ST.. | 2 | | 001-099 |
| 0415 | 20 | GA | | | 1-6 | 31-31-43 | D41307J | | | DL | GD01956 | ST.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0416 | 20 | | GA | | 1-6 | 31-31-43 | D41307J | | | DM | GD01956 | ST.. | 2 | | 001-099 |
| 0417 | 20 | | GA | | 1-6 | 31-31-43 | D41307J | | | DN | GD01956 | ST.. | 2 | | 001-099 |
| 0418 | 20 | | GA | | 1-6 | 31-31-43 | D41307J | | | DO | GD01956 | ST.. | 2 | | 001-099 |
| 0419 | 20 | | GA | | 1-6 | 31-31-43 | D41403J | | | DP | GD01952 | ST.. | 2 | | 001-099 |
| 0420 | 20 | | GA | | 1-6 | 31-31-42 | D41403J | | | AV | GD01952 | ST.. | 2 | | 001-099 |
| 0421 | 22 | | GA | | 2-0 | 31-31-65 | D00011B | J05 | | | GD01956 | ST.. | 2 | | 010-099 |
| 0422 | 22 | | GA | | 2-0 | 31-31-65 | D00011B | K05 | | | GD01956 | ST.. | 2 | | 010-099 |
| 0423 | 22 | | GA | | 2-0 | 31-31-65 | D00011E | J06 | | | GD01956 | ST.. | 2 | | 010-099 |
| 0434 | 20 | | GA | | 1-6 | 31-31-43 | GD01944 | ST.. | 2 | | D41309J | | | DR | 001-002 |
| 0434 | 20 | | GA | | 2-2 | 31-31-43 | D41309J | | | DR | GD03366 | ST.. | 2 | * | 003-099 |
| 0448 | 20 | | GA | | 2-4 | 31-31-02 | D00011A | | | DQ | GD01955 | ST.. | 2 | | 001-009 |
| 0448 | 20 | | GA | | 2-4 | 31-31-02 | D00011A | | | DQ | GD01955 | ST.. | 2 | *1 | 010-099 |
| 0449 | 20 | | GA | | 2-4 | 31-31-02 | D00011A | | | DS | GD01955 | ST.. | 2 | | 001-009 |
| 0449 | 20 | | GA | | 2-4 | 31-31-02 | D00011A | | | DS | GD01955 | ST.. | 2 | *1 | 010-099 |
| 0450 | 20 | | GA | | 2-4 | 31-31-02 | D00011D | | | DT | GD01955 | ST.. | 2 | | 001-099 |
| 0454 | 20 | | GA | | 2-4 | 31-31-02 | D00011A | | | DU | GD01955 | ST.. | 2 | | 001-099 |
| 0455 | 24 | | GK | | 2-7 | 31-31-02 | D00011A | F11 | | | D40255J | | 8 | | 001-009 |
| 0455 | 24 | | GK | | 2-7 | 31-31-02 | D00011A | CAP | Y | | D40255J | | 8 | | 010-099 |
| 0456 | 22 | | GA | | 3-1 | 31-31-02 | D40678J | | 8 | | TB0181Z | | 83 | BJ | 001-099 |
| 0457 | 22 | | GA | | 2-6 | 31-31-02 | D40255J | | 16 | | TB0181Z | | 83 | BJ | 001-099 |
| 0458 | 22 | | GA | | 2-6 | 31-31-02 | D40255J | | 7 | | TB0181Z | | 83 | BJ | 001-099 |
| 0536 | 22 | | GA | | 5-0 | 31-31-61 | D00011A | F07 | | | D43315J | | 4 | | 010-099 |
| 0537 | 22 | | GA | | 5-0 | 31-31-61 | D00011D | G07 | | | D43315J | | 5 | | 010-099 |
| 0538 | 22 | | GA | | 2-4 | 31-31-61 | D00011D | F07 | | | D41307J | | 2 | | 010-099 |
| 0539 | 22 | | GA | | 2-4 | 31-31-61 | D00011A | E07 | | | D41307J | | 1 | | 010-099 |
| 0568 | 22 | | GA | | 5-0 | 34-22-18 | D41307J | | 28 | | SM00002 | | | 9 | 002 |
| 0577 | 22 | | GA | | 4-2 | 31-31-61 | D00011A | D07 | | | D41309J | | 52 | | 010-099 |
| 0578 | 22 | | GA | | 5-0 | 31-31-61 | D00011A | C03 | | | TB0181Y | C003 | BJ | | 010-099 |
| 0580 | 22 | | GA | | 1-11 | 31-31-61 | D41361J | | 24 | | TB0181Y | C003 | BJ | | 010-099 |
| 0581 | 22 | | GA | | 2-9 | 31-31-61 | D43315J | | 6 | | TB0181Y | C003 | BJ | | 010-099 |
| 0586 | 22 | | GA | | 2-3 | 31-31-51 | D00011E | A14 | | | GD01956 | AC.. | 2 | | 010-099 |
| 0587 | 22 | | GA | | 2-3 | 31-31-51 | D00011E | B14 | | | GD01956 | AC.. | 2 | | 010-099 |
| 0588 | 22 | | GA | | 4-2 | 31-31-61 | D00011E | J03 | | | D43309J | | 5 | | 010-099 |
| 0589 | 22 | | GA | | 4-2 | 31-31-61 | D00011E | K03 | | | D43309J | | 6 | | 010-099 |
| 0590 | 22 | | GA | | 4-2 | 31-31-61 | D00011E | J04 | | | D43309J | | 7 | | 010-099 |
| 0591 | 22 | | GA | | 4-2 | 31-31-61 | D00011E | K04 | | | D43309J | | 8 | | 010-099 |
| 0592 | 22 | | GA | | 4-2 | 31-31-61 | D00011B | K02 | | | D43309J | | 1 | | 010-099 |
| 0593 | 22 | | GA | | 4-2 | 31-31-61 | D00011B | J03 | | | D43309J | | 2 | | 010-099 |
| 0594 | 22 | | GA | | 4-2 | 31-31-61 | D00011B | K03 | | | D43309J | | 3 | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 0595 | 22 | | GA | | 4-2 | 31-31-61 | D00011B | J04 | | | D43309J | 4 | | | 010-099 |
| 1001 | 22 | | GT | BS | 5-0 | 31-31-13 | D41523J | 13 | | | D00011A | C11 | | | 115-199 |
| 1001Z | | | | BS | 0-0 | 31-31-13 | D41523J | | | AY | D00011A | DED | | | 115-199 |
| 1002 | 22 | | GT | BT | 5-0 | 31-31-13 | D41523J | 14 | | | D00011A | D11 | | | 115-199 |
| 1002Z | | | | BT | 0-0 | 31-31-13 | D41523J | | | AY | D00011A | DED | | | 115-199 |
| 1003 | 22 | | GT | BU | 5-0 | 31-31-13 | D41523J | 15 | | | D00011A | E11 | | | 115-199 |
| 1003Z | | | | BU | 0-0 | 31-31-13 | D41523J | | | AY | D00011A | DED | | | 115-199 |
| 2001B | 24 | | GL | AH | 2-9 | 23-51-12 | D41309J | 38 | | | D42019J | 16 | | | 001-099 |
| 2001B | 24 | | GL | AH | 3-0 | 23-51-12 | D41309J | 38 | | | D42019J | 16 | | | 115-199 |
| 2001R | 24 | | GL | AH | 0-0 | 23-51-12 | D41309J | 39 | | | D42019J | 15 | | | ALL |
| 2002B | 22 | | GB | BK | 2-1 | 31-31-51 | D41956J | 13 | | | D00011B | F15 | | | 001-099 |
| 2002B | 22 | | GB | BK | 3-0 | 31-31-31 | D41956J | 13 | | | D00011B | F15 | | | 115-199 |
| 2002R | 22 | | GB | BK | 0-0 | 31-31-51 | D41956J | 12 | | | D00011B | F14 | | | 001-099 |
| 2002R | 22 | | GB | BK | 0-0 | 31-31-31 | D41956J | 12 | | | D00011B | F14 | | | 115-199 |
| 2003B | 24 | | GL | BL | 5-0 | 31-31-32 | D41309J | 11 | | | D00011B | B12 | | | 115-199 |
| 2003R | 24 | | GL | BL | 0-0 | 31-31-32 | D41309J | 10 | | | D00011B | B10 | | | 115-199 |
| 2004B | 24 | | GL | BM | 5-0 | 31-31-32 | D41309J | 14 | | | D00011E | B09 | | | 115-199 |
| 2004R | 24 | | GL | BM | 0-0 | 31-31-32 | D41309J | 13 | | | D00011E | B07 | | | 115-199 |
| 2005B | 24 | | GL | BN | 5-0 | 31-31-32 | D41309J | 16 | | | D00011B | C03 | | | 115-199 |
| 2005R | 24 | | GL | BN | 0-0 | 31-31-32 | D41309J | 15 | | | D00011B | C01 | | | 115-199 |
| 2006B | 22 | | GB | CT | 3-0 | 31-31-31 | D40927J | 2 | | | D00011B | B09 | | | 115-199 |
| 2006R | 22 | | GB | CT | 0-0 | 31-31-31 | D40927J | 1 | | | D00011B | B07 | | | 115-199 |
| 2007B | 24 | | GL | CU | 3-9 | 31-31-51 | D00011E | B11 | | | D41443J | 32 | | | 001-099 |
| 2007B | 24 | | GL | CU | 4-0 | 31-31-31 | D41443J | 52 | | | D00011E | B05 | | | 115-199 |
| 2007R | 24 | | GL | CU | 0-0 | 31-31-51 | D00011E | B10 | | | D41443J | 31 | | | 001-099 |
| 2007R | 24 | | GL | CU | 0-0 | 31-31-31 | D41443J | 51 | | | D00011E | B04 | | | 115-199 |
| 2009B | 24 | | GL | EW | 2-9 | 31-31-51 | D00011E | A06 | | | D41145J | 3 | | | 001-099 |
| 2009R | 24 | | GL | EW | 0-0 | 31-31-51 | D00011E | A04 | | | D41145J | 2 | | | 001-099 |
| 2010B | 24 | | GL | EX | 2-9 | 31-31-51 | D00011E | A09 | | | D41145J | 6 | | | 001-099 |
| 2010R | 24 | | GL | EX | 0-0 | 31-31-51 | D00011E | A07 | | | D41145J | 5 | | | 001-099 |
| 2011B | 24 | | GL | EY | 2-9 | 31-31-51 | D00011B | A09 | | | D41145J | 9 | | | 001-099 |
| 2011R | 24 | | GL | EY | 0-0 | 31-31-51 | D00011B | A07 | | | D41145J | 8 | | | 001-099 |
| 2034B | 22 | | GB | QZ | 4-1 | 31-31-51 | D00011E | A15 | | | D41309J | 14 | | | 010-099 |
| 2034R | 22 | | GB | QZ | 0-0 | 31-31-51 | D00011E | A13 | | | D41309J | 13 | | | 010-099 |
| 2035B | 22 | | GB | PZ | 4-1 | 31-31-51 | D00011E | B15 | | | D41309J | 16 | | | 010-099 |
| 2035R | 22 | | GB | PZ | 0-0 | 31-31-51 | D00011E | B13 | | | D41309J | 15 | | | 010-099 |
| 2501B | 24 | | G2 | BP | 2-1 | 31-31-51 | D41956J | 2 | | | D00011B | A02 | | | 001-099 |
| 2501B | 24 | | G2 | BP | 3-0 | 31-31-31 | D41956J | 2 | | | D00011B | A02 | | | 115-199 |
| 2501R | 24 | | G2 | BP | 0-0 | 31-31-51 | D41956J | 1 | | | D00011B | A01 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 2501R | 24 | G2 | | BP | 0-0 | 31-31-31 | D41956J | 1 | | | D00011B | A01 | | | 115-199 |
| 2501Z | | | | BP | 0-0 | 31-31-51 | D41956J | | | BA | D00011B | DED | | | 001-099 |
| 2501Z | | | | BP | 0-0 | 31-31-31 | D41956J | | | BA | D00011B | DED | | | 115-199 |
| 2502B | 24 | G2 | | BQ | 2-1 | 31-31-51 | D41956J | 5 | | | D00011B | A05 | | | 001-099 |
| 2502B | 24 | G2 | | BQ | 3-0 | 31-31-31 | D41956J | 5 | | | D00011B | A05 | | | 115-199 |
| 2502R | 24 | G2 | | BQ | 0-0 | 31-31-51 | D41956J | 4 | | | D00011B | A04 | | | 001-099 |
| 2502R | 24 | G2 | | BQ | 0-0 | 31-31-31 | D41956J | 4 | | | D00011B | A04 | | | 115-199 |
| 2502Z | | | | BQ | 0-0 | 31-31-51 | D41956J | | | BB | D00011B | DED | | | 001-099 |
| 2502Z | | | | BQ | 0-0 | 31-31-31 | D41956J | | | BB | D00011B | DED | | | 115-199 |
| 2503B | 24 | G2 | | BR | 2-1 | 31-31-51 | D41956J | 8 | | | D00011B | B05 | | | 001-099 |
| 2503B | 24 | G2 | | BR | 3-0 | 31-31-31 | D41956J | 8 | | | D00011B | B05 | | | 115-199 |
| 2503R | 24 | G2 | | BR | 0-0 | 31-31-51 | D41956J | 7 | | | D00011B | B04 | | | 001-099 |
| 2503R | 24 | G2 | | BR | 0-0 | 31-31-31 | D41956J | 7 | | | D00011B | B04 | | | 115-199 |
| 2503Z | | | | BR | 0-0 | 31-31-51 | D41956J | | | BC | D00011B | DED | | | 001-099 |
| 2503Z | | | | BR | 0-0 | 31-31-31 | D41956J | | | BC | D00011B | DED | | | 115-199 |
| 3501B | 24 | G3 | | HF | 2-7 | 31-31-02 | D00011A | D11 | | | D40255J | 9 | | | 001-099 |
| 3501R | 24 | G3 | | HF | 0-0 | 31-31-02 | D00011A | C11 | | | D40255J | 10 | | | 001-099 |
| 3501Y | 24 | G3 | | HF | 0-0 | 31-31-02 | D00011A | E11 | | | D40255J | 11 | | | 001-099 |
| 3501Z | | | | HF | 0-0 | 31-31-02 | D00011A | | | DU | D40255J | 12 | | | 001-099 |
| 5001B | 24 | G2 | | AA | 3-7 | 34-53-11 | D41525J | 23 | | | D00251A | F07 | | | 001-099 |
| 5001R | 24 | G2 | | AA | 0-0 | 34-53-11 | D41525J | 22 | | | D00251A | E07 | | | 001-099 |
| 5001Z | | | | AA | 0-0 | 34-53-11 | D41525J | | | AA | D00251A | DED | | | 001-099 |
| 5002B | 24 | G2 | | AB | 3-1 | 34-53-11 | D41309J | 23 | | | D00251A | J07 | | | 001-099 |
| 5002B | 24 | G2 | | AB | 3-0 | 34-53-11 | D41309J | 23 | | | D00251A | J07 | | | 115-199 |
| 5002R | 24 | G2 | | AB | 0-0 | 34-53-11 | D41309J | 22 | | | D00251A | H07 | | | ALL |
| 5002Z | | | | AB | 0-0 | 34-53-11 | D41309J | | | AB | D00251A | DED | | | ALL |
| 5003B | 24 | G2 | | AC | 3-3 | 34-53-11 | D41361J | 2 | | | D00251B | B05 | | | 001-099 |
| 5003B | 24 | G2 | | AC | 4-0 | 34-53-11 | D41361J | 2 | | | D00251B | B05 | | | 115-199 |
| 5003R | 24 | G2 | | AC | 0-0 | 34-53-11 | D41361J | 1 | | | D00251B | A05 | | | ALL |
| 5003Z | | | | AC | 0-0 | 34-53-11 | D41361J | | | AC | D00251B | DED | | | ALL |
| 5004B | 24 | G2 | | AD | 5-0 | 34-45-02 | D41307J | 46 | | | D00251A | F05 | | | 001-099 |
| 5004B | 24 | G2 | | GE | 6-0 | 34-45-02 | D41307J | 46 | | | D00251A | F05 | | | 115-199 |
| 5004R | 24 | G2 | | AD | 0-0 | 34-45-02 | D41307J | 45 | | | D00251A | E05 | | | 001-099 |
| 5004R | 24 | G2 | | GE | 0-0 | 34-45-02 | D41307J | 45 | | | D00251A | E05 | | | 115-199 |
| 5004Z | | | | AD | 0-0 | 34-45-02 | D41307J | | | BY | D00251A | DED | | | 001-099 |
| 5004Z | | | | GE | 0-0 | 34-45-02 | D41307J | | | BY | D00251A | DED | | | 115-199 |
| 5005B | 24 | G2 | | AE | 5-0 | 34-45-02 | D41307J | 53 | | | D00251A | H05 | | | 001-099 |
| 5005B | 24 | G2 | | GF | 6-0 | 34-45-02 | D41307J | 53 | | | D00251A | H05 | | | 115-199 |
| 5005R | 24 | G2 | | AE | 0-0 | 34-45-02 | D41307J | 52 | | | D00251A | G05 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | | |
| 5005R | 24 | G2 | GF | | 0-0 | 34-45-02 | D41307J | 52 | | | | D00251A | G05 | | | 115-199 |
| 5005Z | | | AE | | 0-0 | 34-45-02 | D41307J | | | BZ | | D00251A | DED | | | 001-099 |
| 5005Z | | | GF | | 0-0 | 34-45-02 | D41307J | | | BZ | | D00251A | DED | | | 115-199 |
| 5006B | 24 | G2 | AL | | 2-5 | 34-55-11 | D42019J | 20 | | | | D00239B | E03 | | | 001-099 |
| 5006B | 24 | G2 | AL | | 3-0 | 34-55-11 | D42019J | 20 | | | | D00239B | E03 | | | 115-199 |
| 5006R | 24 | G2 | AL | | 0-0 | 34-55-11 | D42019J | 19 | | | | D00239B | D03 | | | ALL |
| 5006Z | | | AL | | 0-0 | 34-55-11 | D42019J | | | AF | | D00239B | DED | | | ALL |
| 5007B | 24 | G2 | AM | | 2-2 | 34-55-11 | D41309J | 43 | | | | D00239B | B03 | | | 001-099 |
| 5007B | 24 | G2 | AM | | 3-0 | 34-55-11 | D41309J | 43 | | | | D00239B | B03 | | | 115-199 |
| 5007R | 24 | G2 | AM | | 0-0 | 34-55-11 | D41309J | 42 | | | | D00239B | A03 | | | ALL |
| 5007Z | | | AM | | 0-0 | 34-55-11 | D41309J | | | AG | | D00239B | DED | | | ALL |
| 5008B | 24 | G2 | AN | | 2-2 | 34-61-12 | D41309J | 8 | | | | D00239B | H01 | | | 001-099 |
| 5008B | 24 | G2 | AN | | 3-0 | 34-61-12 | D41309J | 8 | | | | D00239B | H01 | | | 115-199 |
| 5008R | 24 | G2 | AN | | 0-0 | 34-61-12 | D41309J | 7 | | | | D00239B | G01 | | | ALL |
| 5008Z | | | AN | | 0-0 | 34-61-12 | D41309J | | | AH | | D00239B | DED | | | ALL |
| 5009B | 24 | G2 | AP | | 2-2 | 34-22-19 | D41309J | 5 | | | | D00239B | H03 | | | 001-099 |
| 5009B | 24 | G2 | AP | | 3-0 | 34-22-19 | D41309J | 5 | | | | D00239B | H03 | | | 115-199 |
| 5009R | 24 | G2 | AP | | 0-0 | 34-22-19 | D41309J | 4 | | | | D00239B | G03 | | | ALL |
| 5009Z | | | AP | | 0-0 | 34-22-19 | D41309J | | | AI | | D00239B | DED | | | ALL |
| 5011B | 24 | G2 | AQ | | 3-0 | 31-31-11 | D41519J | 11 | | | | D00011A | H11 | | | 115-199 |
| 5011R | 24 | G2 | AQ | | 0-0 | 31-31-11 | D41519J | 10 | | | | D00011A | G11 | | | 115-199 |
| 5011Z | | | AQ | | 0-0 | 31-31-11 | D41519J | | | AJ | | D00011A | DED | | | 115-199 |
| 5012B | 24 | G2 | AR | | 2-7 | 31-31-01 | D41519J | 15 | | | | D00011A | K09 | | | 001-099 |
| 5012B | 24 | G2 | AR | | 3-0 | 31-31-11 | D41519J | 15 | | | | D00011A | K09 | | | 115-199 |
| 5012R | 24 | G2 | AR | | 0-0 | 31-31-01 | D41519J | 14 | | | | D00011A | J09 | | | 001-099 |
| 5012R | 24 | G2 | AR | | 0-0 | 31-31-11 | D41519J | 14 | | | | D00011A | J09 | | | 115-199 |
| 5012Z | | | AR | | 0-0 | 31-31-01 | D41519J | | | AK | | D00011A | DED | | | 001-099 |
| 5012Z | | | AR | | 0-0 | 31-31-11 | D41519J | | | AK | | D00011A | DED | | | 115-199 |
| 5013B | 24 | G2 | AS | | 3-0 | 31-31-11 | D41519J | 17 | | | | D00011A | H09 | | | 115-199 |
| 5013R | 24 | G2 | AS | | 0-0 | 31-31-11 | D41519J | 16 | | | | D00011A | G09 | | | 115-199 |
| 5013Z | | | AS | | 0-0 | 31-31-11 | D41519J | | | AL | | D00011A | DED | | | 115-199 |
| 5014B | 24 | G2 | AT | | 2-5 | 31-31-01 | D41521J | 2 | | | | TB0181Y | C102 | BJ | | 001-099 |
| 5014B | 24 | G2 | AT | | 3-0 | 31-31-11 | D41521J | 2 | | | | TB0181Y | C102 | BJ | | 115-199 |
| 5014R | 24 | G2 | AT | | 0-0 | 31-31-01 | D41521J | 1 | | | | TB0181Y | A102 | BJ | | 001-099 |
| 5014R | 24 | G2 | AT | | 0-0 | 31-31-11 | D41521J | 1 | | | | TB0181Y | A102 | BJ | | 115-199 |
| 5014Z | | | AT | | 0-0 | 31-31-01 | D41521J | 3 | | | | GD01954 | ST.. | 2 | | 001-099 |
| 5014Z | | | AT | | 0-0 | 31-31-11 | D41521J | 3 | | | | GD01954 | ST.. | 2 | | 115-199 |
| 5015B | 24 | G2 | AU | | 2-4 | 31-31-01 | D41521J | 8 | | | | D00011A | K11 | | | 001-099 |
| 5015B | 24 | G2 | AU | | 3-0 | 31-31-11 | D41521J | 8 | | | | D00011A | K11 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | | To | | | | |
|--------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5015R | 24 | G2 | AU | | 0-0 | 31-31-01 | D41521J | 7 | | | D00011A | J11 | | | 001-099 |
| 5015R | 24 | G2 | AU | | 0-0 | 31-31-11 | D41521J | 7 | | | D00011A | J11 | | | 115-199 |
| 5015Z | | | AU | | 0-0 | 31-31-01 | D41521J | | | AN | D00011A | DED | | | 001-099 |
| 5015Z | | | AU | | 0-0 | 31-31-11 | D41521J | | | AN | D00011A | DED | | | 115-199 |
| 5016B | 24 | G2 | AV | | 3-10 | 31-31-41 | D41443J | 10 | | | D00011A | B14 | | | 001-099 |
| 5016B | 24 | G2 | AV | | 4-0 | 31-31-21 | D41443J | 10 | | | D00011A | B14 | | | 115-199 |
| 5016R | 24 | G2 | AV | | 0-0 | 31-31-41 | D41443J | 11 | | | D00011A | A14 | | | 001-099 |
| 5016R | 24 | G2 | AV | | 0-0 | 31-31-21 | D41443J | 11 | | | D00011A | A14 | | | 115-199 |
| 5016Z | | | AV | | 0-0 | 31-31-41 | D41443J | | | AP | D00011A | DED | | | 001-099 |
| 5016Z | | | AV | | 0-0 | 31-31-21 | D41443J | | | AP | D00011A | DED | | | 115-199 |
| 5017B | 24 | G2 | AW | | 5-0 | 31-31-41 | D41309J | 50 | | | D00011A | F13 | | | 001-099 |
| 5017B | 24 | G2 | AW | | 5-0 | 31-31-21 | D41309J | 50 | | | D00011A | F13 | | | 115-199 |
| 5017R | 24 | G2 | AW | | 0-0 | 31-31-41 | D41309J | 49 | | | D00011A | E13 | | | 001-099 |
| 5017R | 24 | G2 | AW | | 0-0 | 31-31-21 | D41309J | 49 | | | D00011A | E13 | | | 115-199 |
| 5017Z | | | AW | | 0-0 | 31-31-41 | D41309J | | | AQ | D00011A | DED | | | 001-099 |
| 5017Z | | | AW | | 0-0 | 31-31-21 | D41309J | | | AQ | D00011A | DED | | | 115-199 |
| 5018B | 24 | G2 | AX | | 3-10 | 31-31-42 | D41443J | 52 | | | D00011A | D14 | | | 001-099 |
| 5018B | 24 | G2 | AX | | 5-0 | 31-31-21 | D41309J | 29 | | | D00011A | F14 | | | 115-199 |
| 5018R | 24 | G2 | AX | | 0-0 | 31-31-42 | D41443J | 51 | | | D00011A | C14 | | | 001-099 |
| 5018R | 24 | G2 | AX | | 0-0 | 31-31-21 | D41309J | 28 | | | D00011A | E14 | | | 115-199 |
| 5018Z | | | AX | | 0-0 | 31-31-42 | D41443J | | | AR | D00011A | DED | | | 001-099 |
| 5018Z | | | AX | | 0-0 | 31-31-21 | D41309J | | | AR | D00011A | DED | | | 115-199 |
| 5019B | 24 | G2 | AY | | 4-2 | 31-31-41 | D41309J | 26 | | | D00011A | H13 | | | 001-099 |
| 5019B | 24 | G2 | AY | | 5-0 | 31-31-21 | D41309J | 26 | | | D00011A | H13 | | | 115-199 |
| 5019R | 24 | G2 | AY | | 0-0 | 31-31-41 | D41309J | 25 | | | D00011A | G13 | | | 001-099 |
| 5019R | 24 | G2 | AY | | 0-0 | 31-31-21 | D41309J | 25 | | | D00011A | G13 | | | 115-199 |
| 5019Z | | | AY | | 0-0 | 31-31-41 | D41309J | | | AS | D00011A | DED | | | 001-099 |
| 5019Z | | | AY | | 0-0 | 31-31-21 | D41309J | | | AS | D00011A | DED | | | 115-199 |
| 5020B | 24 | G2 | AZ | | 3-10 | 31-31-41 | D00011D | D14 | | | D41443J | 18 | | | 001-099 |
| 5020B | 24 | G2 | AZ | | 4-0 | 31-31-21 | D41443J | 18 | | | D00011D | D14 | | | 115-199 |
| 5020R | 24 | G2 | AZ | | 0-0 | 31-31-41 | D00011D | C14 | | | D41443J | 19 | | | 001-099 |
| 5020R | 24 | G2 | AZ | | 0-0 | 31-31-21 | D41443J | 19 | | | D00011D | C14 | | | 115-199 |
| 5020Z | | | AZ | | 0-0 | 31-31-41 | D00011D | DED | | | D41443J | | | AT | 001-099 |
| 5020Z | | | AZ | | 0-0 | 31-31-21 | D41443J | | | AT | D00011D | DED | | | 115-199 |
| 5021B | 24 | G2 | BA | | 3-7 | 31-31-43 | D00011A | K13 | | | D41361J | 37 | | | 001-099 |
| 5021R | 24 | G2 | BA | | 0-0 | 31-31-43 | D00011A | J13 | | | D41361J | 36 | | | 001-099 |
| 5021Z | | | BA | | 0-0 | 31-31-43 | D00011A | DED | | | D41361J | | | DG | 001-099 |
| 5022B | 24 | G2 | BB | | 5-0 | 31-31-22 | D41309J | 31 | | | D00011A | K13 | | | 115-199 |
| 5022R | 24 | G2 | BB | | 0-0 | 31-31-22 | D41309J | 32 | | | D00011A | J13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5022Z | | | | BB | 0-0 | 31-31-22 | D41309J | | | | BU | D00011A | DED | | 115-199 |
| 5024B | 24 | G2 | | BD | 2-4 | 31-31-43 | D00011D | H13 | | | | D41307J | 39 | | 001-099 |
| 5024R | 24 | G2 | | BD | 0-0 | 31-31-43 | D00011D | G13 | | | | D41307J | 38 | | 001-099 |
| 5024Z | | | | BD | 0-0 | 31-31-43 | D00011D | DED | | | | D41307J | | DM | 001-099 |
| 5025B | 24 | G2 | | BE | 4-0 | 31-31-22 | D41361J | 8 | | | | D00011D | H13 | | 115-199 |
| 5025R | 24 | G2 | | BE | 0-0 | 31-31-22 | D41361J | 9 | | | | D00011D | G13 | | 115-199 |
| 5025Z | | | | BE | 0-0 | 31-31-22 | D41361J | | | | BV | D00011D | DED | | 115-199 |
| 5027B | 24 | G2 | | BG | 2-4 | 31-31-43 | D41307J | 50 | | | | D00011D | F10 | | 001-099 |
| 5027B | 24 | G2 | | BG | 5-0 | 31-31-22 | D41309J | 54 | | | | D00011D | B14 | | 115-199 |
| 5027R | 24 | G2 | | BG | 0-0 | 31-31-43 | D41307J | 49 | | | | D00011D | E10 | | 001-099 |
| 5027R | 24 | G2 | | BG | 0-0 | 31-31-22 | D41309J | 53 | | | | D00011D | A14 | | 115-199 |
| 5027Z | | | | BG | 0-0 | 31-31-43 | D41307J | | | | DN | D00011D | DED | | 001-099 |
| 5027Z | | | | BG | 0-0 | 31-31-22 | D41309J | | | | AU | D00011D | DED | | 115-199 |
| 5028B | 24 | G2 | | BH | 2-8 | 31-31-42 | D41403J | 2 | | | | D00011D | F13 | | 001-099 |
| 5028B | 24 | G2 | | BH | 3-0 | 31-31-22 | D41403J | 2 | | | | D00011D | F13 | | 115-199 |
| 5028R | 24 | G2 | | BH | 0-0 | 31-31-42 | D41403J | 1 | | | | D00011D | E13 | | 001-099 |
| 5028R | 24 | G2 | | BH | 0-0 | 31-31-22 | D41403J | 1 | | | | D00011D | E13 | | 115-199 |
| 5028Z | | | | BH | 0-0 | 31-31-42 | D41403J | | | | AV | D00011D | DED | | 001-099 |
| 5028Z | | | | BH | 0-0 | 31-31-22 | D41403J | | | | AV | D00011D | DED | | 115-199 |
| 5031B | 24 | G2 | | BV | 5-0 | 31-31-13 | D41523J | 11 | | | | D00011D | F15 | | 115-199 |
| 5031R | 24 | G2 | | BV | 0-0 | 31-31-13 | D41523J | 10 | | | | D00011D | E15 | | 115-199 |
| 5031Z | | | | BV | 0-0 | 31-31-13 | D41523J | | | | AZ | D00011D | DED | | 115-199 |
| 5032B | 24 | G2 | | BW | 3-0 | 31-31-13 | D00777A | A02 | | | | TB0181X | A100 | BJ | 115-199 |
| 5032R | 24 | G2 | | BW | 0-0 | 31-31-13 | D00777A | A01 | | | | TB0181X | A099 | BJ | 115-199 |
| 5032Z | | | | BW | 0-0 | 31-31-13 | D00777A | DED | | | | GD01953 | ST.. | 2 | 115-199 |
| 5033B | 24 | G2 | | BX | 3-0 | 31-31-13 | D00777A | D02 | | | | TB0181X | B100 | BJ | 115-199 |
| 5033R | 24 | G2 | | BX | 0-0 | 31-31-13 | D00777A | D01 | | | | TB0181X | B099 | BJ | 115-199 |
| 5033Z | | | | BX | 0-0 | 31-31-13 | D00777A | DED | | | | GD01953 | ST.. | 2 | 115-199 |
| 5034B | 24 | G2 | | BY | 3-0 | 31-31-13 | D00777A | G02 | | | | TB0181X | C100 | BJ | 115-199 |
| 5034R | 24 | G2 | | BY | 0-0 | 31-31-13 | D00777A | G01 | | | | TB0181X | C099 | BJ | 115-199 |
| 5034Z | | | | BY | 0-0 | 31-31-13 | D00777A | DED | | | | GD01953 | ST.. | 2 | 115-199 |
| 5035B | 24 | G2 | | BZ | 3-0 | 31-31-13 | D00777A | K02 | | | | TB0181X | D100 | BJ | 115-199 |
| 5035R | 24 | G2 | | BZ | 0-0 | 31-31-13 | D00777A | K01 | | | | TB0181X | D099 | BJ | 115-199 |
| 5035Z | | | | BZ | 0-0 | 31-31-13 | D00777A | DED | | | | GD01953 | ST.. | 2 | 115-199 |
| 5036B | 24 | G2 | | CA | 3-0 | 31-31-13 | D00011A | D09 | | | | TB0181X | A100 | BJ | 115-199 |
| 5036R | 24 | G2 | | CA | 0-0 | 31-31-13 | D00011A | C09 | | | | TB0181X | A099 | BJ | 115-199 |
| 5036Z | | | | CA | 0-0 | 31-31-13 | D00011A | DED | | | | GD01953 | ST.. | 2 | 115-199 |
| 5037B | 24 | G2 | | CB | 3-0 | 31-31-13 | D00011A | K02 | | | | TB0181X | B100 | BJ | 115-199 |
| 5037R | 24 | G2 | | CB | 0-0 | 31-31-13 | D00011A | J02 | | | | TB0181X | B099 | BJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | |
| 5037Z | | | | CB | 0-0 | 31-31-13 | D00011A | DED | | | GD01953 | ST.. | 2 | | 115-199 |
| 5038B | 24 | G2 | | CC | 3-0 | 31-31-13 | D00011A | D10 | | | TB0181X | C100 | BJ | | 115-199 |
| 5038R | 24 | G2 | | CC | 0-0 | 31-31-13 | D00011A | C10 | | | TB0181X | C099 | BJ | | 115-199 |
| 5038Z | | | | CC | 0-0 | 31-31-13 | D00011A | DED | | | GD01953 | ST.. | 2 | | 115-199 |
| 5039B | 24 | G2 | | CD | 3-7 | 31-31-43 | D00011D | H10 | | | D41361J | 18 | | | 001-009 |
| 5039B | 24 | G2 | | CD | 3-0 | 31-31-13 | D00011A | F10 | | | TB0181X | D100 | BJ | | 115-199 |
| 5039R | 24 | G2 | | CD | 0-0 | 31-31-43 | D00011D | G10 | | | D41361J | 17 | | | 001-009 |
| 5039R | 24 | G2 | | CD | 0-0 | 31-31-13 | D00011A | E10 | | | TB0181X | D099 | BJ | | 115-199 |
| 5039Z | | | | CD | 0-0 | 31-31-43 | D00011D | DED | | | D41361J | | | DH | 001-009 |
| 5039Z | | | | CD | 0-0 | 31-31-13 | D00011A | DED | | | GD01953 | ST.. | 2 | | 115-199 |
| 5040B | 24 | G2 | | BO | 4-0 | SPARE | D41361J | 18 | | | D00011D | F14 | | | 115-199 |
| 5040R | 24 | G2 | | BO | 0-0 | SPARE | D41361J | 17 | | | D00011D | E14 | | | 115-199 |
| 5040Z | | | | BO | 0-0 | SPARE | D41361J | | | BD | D00011D | DED | | | 115-199 |
| 5041B | 24 | G2 | | CE | 3-0 | 31-31-22 | D41307J | 2 | | | D00011A | D13 | | | 115-199 |
| 5041R | 24 | G2 | | CE | 0-0 | 31-31-22 | D41307J | 1 | | | D00011A | C13 | | | 115-199 |
| 5041Z | | | | CE | 0-0 | 31-31-22 | D41307J | | | BE | D00011A | DED | | | 115-199 |
| 5042B | 24 | G2 | | CF | 3-0 | 31-31-22 | D41307J | 6 | | | D00011A | B15 | | | 115-199 |
| 5042R | 24 | G2 | | CF | 0-0 | 31-31-22 | D41307J | 5 | | | D00011A | A15 | | | 115-199 |
| 5042Z | | | | CF | 0-0 | 31-31-22 | D41307J | | | BF | D00011A | DED | | | 115-199 |
| 5043B | 24 | G2 | | CG | 4-0 | 31-31-22 | D41361J | 20 | | | D00011D | D13 | | | 115-199 |
| 5043R | 24 | G2 | | CG | 0-0 | 31-31-22 | D41361J | 19 | | | D00011D | C13 | | | 115-199 |
| 5043Z | | | | CG | 0-0 | 31-31-22 | D41361J | | | BG | D00011D | DED | | | 115-199 |
| 5044B | 24 | G2 | | CH | 4-0 | 31-31-22 | D41361J | 24 | | | D00011D | K14 | | | 115-199 |
| 5044R | 24 | G2 | | CH | 0-0 | 31-31-22 | D41361J | 23 | | | D00011D | J14 | | | 115-199 |
| 5044Z | | | | CH | 0-0 | 31-31-22 | D41361J | | | BH | D00011D | DED | | | 115-199 |
| 5045B | 24 | G2 | | CI | 4-0 | 31-31-22 | D41361J | 27 | | | D00011D | D15 | | | 115-199 |
| 5045R | 24 | G2 | | CI | 0-0 | 31-31-22 | D41361J | 26 | | | D00011D | C15 | | | 115-199 |
| 5045Z | | | | CI | 0-0 | 31-31-22 | D41361J | | | BI | D00011D | DED | | | 115-199 |
| 5046B | 24 | G2 | | CJ | 3-0 | 31-31-22 | D41403J | 6 | | | D00011A | D15 | | | 115-199 |
| 5046R | 24 | G2 | | CJ | 0-0 | 31-31-22 | D41403J | 5 | | | D00011A | C15 | | | 115-199 |
| 5046Z | | | | CJ | 0-0 | 31-31-22 | D41403J | | | BJ | D00011A | DED | | | 115-199 |
| 5047B | 24 | G2 | | CK | 2-4 | 31-31-43 | D41307J | 36 | | | D00011A | H14 | | | 001-099 |
| 5047B | 24 | G2 | | CK | 3-0 | 31-31-22 | D41403J | 9 | | | D00011A | H14 | | | 115-199 |
| 5047R | 24 | G2 | | CK | 0-0 | 31-31-43 | D41307J | 35 | | | D00011A | G14 | | | 001-099 |
| 5047R | 24 | G2 | | CK | 0-0 | 31-31-22 | D41403J | 8 | | | D00011A | G14 | | | 115-199 |
| 5047Z | | | | CK | 0-0 | 31-31-43 | D41307J | | | DK | D00011A | DED | | | 001-099 |
| 5047Z | | | | CK | 0-0 | 31-31-22 | D41403J | | | BK | D00011A | DED | | | 115-199 |
| 5048B | 24 | G2 | | CL | 4-0 | 31-31-22 | D41443J | 46 | | | D00011A | D14 | | | 115-199 |
| 5048R | 24 | G2 | | CL | 0-0 | 31-31-22 | D41443J | 45 | | | D00011A | C14 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | | To | | | | | | | | | | | |
|------------|-------------|----|----|-------------------------------|----------|----------|---------|----|------|-------|---------|-------|------|------|--------|-------|------|------|---------|-------------|----|---------|
| | | | | | Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | | | | | | | | |
| 5048Z | | | | CL | 0-0 | 31-31-22 | D41443J | | | | | | | | | | | BL | D00011A | DED | | 115-199 |
| 5049B | 24 | G2 | CM | | 2-8 | 31-31-42 | D41403J | | 5 | | | | | | | | | | D00011D | K13 | | 001-099 |
| 5049B | 24 | G2 | CM | | 5-0 | 31-31-22 | D42019J | | 27 | | | | | | | | | | D00011D | K13 | | 115-199 |
| 5049R | 24 | G2 | CM | | 0-0 | 31-31-42 | D41403J | | 4 | | | | | | | | | | D00011D | J13 | | 001-099 |
| 5049R | 24 | G2 | CM | | 0-0 | 31-31-22 | D42019J | | 28 | | | | | | | | | | D00011D | J13 | | 115-199 |
| 5049Z | | | | CM | 0-0 | 31-31-42 | D41403J | | | | | | | | | | | DD | D00011D | DED | | 001-099 |
| 5049Z | | | | CM | 0-0 | 31-31-22 | D42019J | | | | | | | | | | | BM | D00011D | DED | | 115-199 |
| 5050B | 24 | G2 | CN | | 3-0 | 31-31-22 | D41307J | | 8 | | | | | | | | | | D00011A | K14 | | 115-199 |
| 5050R | 24 | G2 | CN | | 0-0 | 31-31-22 | D41307J | | 7 | | | | | | | | | | D00011A | J14 | | 115-199 |
| 5050Z | | | | CN | 0-0 | 31-31-22 | D41307J | | | | | | | | | | | BN | D00011A | DED | | 115-199 |
| 5051B | 24 | G2 | CP | | 4-0 | 31-31-22 | D41361J | | 29 | | | | | | | | | | D00011D | H14 | | 115-199 |
| 5051R | 24 | G2 | CP | | 0-0 | 31-31-22 | D41361J | | 28 | | | | | | | | | | D00011D | G14 | | 115-199 |
| 5051Z | | | | CP | 0-0 | 31-31-22 | D41361J | | | | | | | | | | | BP | D00011D | DED | | 115-199 |
| 5052B | 24 | G2 | CQ | | 3-0 | 31-31-22 | D41403J | | 11 | | | | | | | | | | D00011D | B15 | | 115-199 |
| 5052R | 24 | G2 | CQ | | 0-0 | 31-31-22 | D41403J | | 10 | | | | | | | | | | D00011D | A15 | | 115-199 |
| 5052Z | | | | CQ | 0-0 | 31-31-22 | D41403J | | | | | | | | | | | BQ | D00011D | DED | | 115-199 |
| 5053B | 24 | G2 | CR | | 4-2 | 31-31-42 | D41309J | | 54 | | | | | | | | | | D00011A | D13 | | 001-099 |
| 5053B | 24 | G2 | CR | | 3-0 | 31-31-23 | TB0181Y | | C117 | BJ | | | | | | | | | D00011A | B13 | | 115-199 |
| 5053R | 24 | G2 | CR | | 0-0 | 31-31-42 | D41309J | | 53 | | | | | | | | | | D00011A | C13 | | 001-099 |
| 5053R | 24 | G2 | CR | | 0-0 | 31-31-23 | TB0181Y | | A117 | BJ | | | | | | | | | D00011A | A13 | | 115-199 |
| 5053Z | | | | CR | 0-0 | 31-31-42 | D41309J | | | | | | | | | | | AU | D00011A | DED | | 001-099 |
| 5053Z | | | | CR | 0-0 | 31-31-23 | GD01956 | | ST.. | 2 | | | | | | | | | D00011A | DED | | 115-199 |
| 5054B | 24 | G2 | CS | | 3-7 | 31-31-42 | D41361J | | 53 | | | | | | | | | | D00011D | K10 | | 001-099 |
| 5054B | 24 | G2 | CS | | 3-0 | 31-31-23 | TB0181Y | | C118 | BJ | | | | | | | | | D00011D | B13 | | 115-199 |
| 5054R | 24 | G2 | CS | | 0-0 | 31-31-42 | D41361J | | 52 | | | | | | | | | | D00011D | J10 | | 001-099 |
| 5054R | 24 | G2 | CS | | 0-0 | 31-31-23 | TB0181Y | | A118 | BJ | | | | | | | | | D00011D | A13 | | 115-199 |
| 5054Z | | | | CS | 0-0 | 31-31-42 | D41361J | | | | | | | | | | | DA | D00011D | DED | | 001-099 |
| 5054Z | | | | CS | 0-0 | 31-31-23 | GD01956 | | ST.. | 2 | | | | | | | | | D00011D | DED | | 115-199 |
| 5055B | 24 | G2 | CV | | 2-0 | 31-31-01 | D41519J | | 9 | | | | | | | | | | TB0181Y | C102 | BJ | 001-099 |
| 5055B | 24 | G2 | CV | | 3-0 | 31-31-11 | D41519J | | 9 | | | | | | | | | | TB0181Y | C102 | BJ | 115-199 |
| 5055R | 24 | G2 | CV | | 0-0 | 31-31-01 | D41519J | | 8 | | | | | | | | | | TB0181Y | A102 | BJ | 001-099 |
| 5055R | 24 | G2 | CV | | 0-0 | 31-31-11 | D41519J | | 8 | | | | | | | | | | TB0181Y | A102 | BJ | 115-199 |
| 5055Z | | | | CV | 0-0 | 31-31-01 | D41519J | | 21 | | | | | | | | | | GD01954 | ST.. | 2 | 001-099 |
| 5055Z | | | | CV | 0-0 | 31-31-11 | D41519J | | 21 | | | | | | | | | | GD01954 | ST.. | 2 | 115-199 |
| 5056B | 24 | G2 | CW | | 2-8 | 31-31-01 | D00011A | | B09 | | | | | | | | | | TB0181Y | C102 | BJ | 001-099 |
| 5056B | 24 | G2 | CW | | 3-0 | 31-31-11 | D00011A | | B09 | | | | | | | | | | TB0181Y | C102 | BJ | 115-199 |
| 5056R | 24 | G2 | CW | | 0-0 | 31-31-01 | D00011A | | A09 | | | | | | | | | | TB0181Y | A102 | BJ | 001-099 |
| 5056R | 24 | G2 | CW | | 0-0 | 31-31-11 | D00011A | | A09 | | | | | | | | | | TB0181Y | A102 | BJ | 115-199 |
| 5056Z | | | | CW | 0-0 | 31-31-01 | D00011A | | DED | | | | | | | | | | GD01954 | ST.. | 2 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 22

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| 5056Z | | | | CW | 0-0 | 31-31-11 | D00011A | DED | | | GD01954 | ST.. | 2 | | 115-199 |
| 5057B | 20 | | QJ | CX | 2-2 | 31-31-44 | D41307J | 22 | | | TB0181X | B112 | BJ | | 001-099 |
| 5057B | 24 | | G2 | CX | 3-0 | 31-31-23 | D41307J | 22 | | | TB0181X | B112 | BJ | | 115-199 |
| 5057R | 20 | | QJ | CX | 0-0 | 31-31-44 | D41307J | 21 | | | TB0181X | A112 | BJ | | 001-099 |
| 5057R | 24 | | G2 | CX | 0-0 | 31-31-23 | D41307J | 21 | | | TB0181X | A112 | BJ | | 115-199 |
| 5057Z | | | | CX | 0-0 | 31-31-44 | D41307J | 23 | | | GD01954 | ST.. | 2 | | 001-099 |
| 5057Z | | | | CX | 0-0 | 31-31-23 | D41307J | 23 | | | GD01954 | ST.. | 2 | | 115-199 |
| 5058B | 20 | | QJ | CY | 3-4 | 31-31-44 | D41361J | 45 | | | TB0181X | D112 | BJ | | 001-099 |
| 5058B | 24 | | G2 | CY | 4-0 | 31-31-23 | D41361J | 45 | | | TB0181X | D112 | BJ | | 115-199 |
| 5058R | 20 | | QJ | CY | 0-0 | 31-31-44 | D41361J | 44 | | | TB0181X | C112 | BJ | | 001-099 |
| 5058R | 24 | | G2 | CY | 0-0 | 31-31-23 | D41361J | 44 | | | TB0181X | C112 | BJ | | 115-199 |
| 5058Z | | | | CY | 0-0 | 31-31-44 | D41361J | 46 | | | GD01954 | ST.. | 2 | | 001-099 |
| 5058Z | | | | CY | 0-0 | 31-31-23 | D41361J | 46 | | | GD01954 | ST.. | 2 | | 115-199 |
| 5061B | 24 | | G2 | DC | 2-8 | 31-31-42 | D00011D | B12 | | | D41403J | 14 | | | 001-099 |
| 5061R | 24 | | G2 | DC | 0-0 | 31-31-42 | D00011D | A12 | | | D41403J | 13 | | | 001-099 |
| 5061Z | | | | DC | 0-0 | 31-31-42 | D00011D | DED | | | D41403J | | | DB | 001-099 |
| 5063B | 24 | | G2 | DE | 4-11 | 31-31-42 | D00011D | D13 | | | D42019J | 29 | | | 001-099 |
| 5063R | 24 | | G2 | DE | 0-0 | 31-31-42 | D00011D | C13 | | | D42019J | 28 | | | 001-099 |
| 5063Z | | | | DE | 0-0 | 31-31-42 | D00011D | DED | | | D42019J | | | DC | 001-099 |
| 5065B | 24 | | G2 | DG | 2-8 | 31-31-43 | D00011A | K14 | | | D41403J | 8 | | | 001-099 |
| 5065R | 24 | | G2 | DG | 0-0 | 31-31-43 | D00011A | J14 | | | D41403J | 7 | | | 001-099 |
| 5065Z | | | | DG | 0-0 | 31-31-43 | D00011A | DED | | | D41403J | | | DI | 001-099 |
| 5067B | 24 | | G2 | DJ | 2-8 | 31-31-43 | D00011D | B15 | | | D41403J | 11 | | | 001-099 |
| 5067R | 24 | | G2 | DJ | 0-0 | 31-31-43 | D00011D | A15 | | | D41403J | 10 | | | 001-099 |
| 5067Z | | | | DJ | 0-0 | 31-31-43 | D00011D | DED | | | D41403J | | | DP | 001-099 |
| 5069B | 24 | | G2 | DL | 2-4 | 31-31-43 | D00011D | K14 | | | D41307J | 7 | | | 001-099 |
| 5069R | 24 | | G2 | DL | 0-0 | 31-31-43 | D00011D | J14 | | | D41307J | 6 | | | 001-099 |
| 5069Z | | | | DL | 0-0 | 31-31-43 | D00011D | DED | | | D41307J | | | DO | 001-099 |
| 5071B | 24 | | G2 | DN | 2-4 | 31-31-43 | D00011A | D15 | | | D41307J | 32 | | | 001-099 |
| 5071R | 24 | | G2 | DN | 0-0 | 31-31-43 | D00011A | C15 | | | D41307J | 31 | | | 001-099 |
| 5071Z | | | | DN | 0-0 | 31-31-43 | D00011A | DED | | | D41307J | | | DL | 001-099 |
| 5072B | 24 | | G2 | DP | 3-7 | 31-31-43 | D00011A | B15 | | | D41361J | 29 | | | 001-099 |
| 5072R | 24 | | G2 | DP | 0-0 | 31-31-43 | D00011A | A15 | | | D41361J | 28 | | | 001-099 |
| 5072Z | | | | DP | 0-0 | 31-31-43 | D00011A | DED | | | D41361J | | | DJ | 001-099 |
| 5074B | 24 | | G2 | DR | 3-7 | 31-31-43 | D00011D | D15 | | | D41361J | 22 | | | 001-099 |
| 5074R | 24 | | G2 | DR | 0-0 | 31-31-43 | D00011D | C15 | | | D41361J | 21 | | | 001-099 |
| 5074Z | | | | DR | 0-0 | 31-31-43 | D00011D | DED | | | D41361J | | | DF | 001-099 |
| 5075B | 24 | | G2 | DS | 3-7 | 31-31-43 | D00011D | H14 | | | D41361J | 26 | | | 001-099 |
| 5075R | 24 | | G2 | DS | 0-0 | 31-31-43 | D00011D | G14 | | | D41361J | 25 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 23

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | | 286N1433 | | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | |
| 5075Z | | | | DS | 0-0 | 31-31-43 | D00011D | DED | | | D41361J | | | DE | 001-099 |
| 5105B | 22 | GU | DW | | 5-0 | 31-31-41 | D00011D | H10 | | | D43315J | 2 | | | 010-099 |
| 5105R | 22 | GU | DW | | 0-0 | 31-31-41 | D00011D | G10 | | | D43315J | 1 | | | 010-099 |
| 5105Z | | | DW | | 0-0 | 31-31-41 | D00011D | DED | | | D43315J | | DW | | 010-099 |
| 5127B | 22 | GU | GR | | 2-4 | 31-31-42 | D00011D | D12 | | | D41307J | 25 | | | 010-099 |
| 5127R | 22 | GU | GR | | 0-0 | 31-31-42 | D00011D | C12 | | | D41307J | 24 | | | 010-099 |
| 5127Z | | | GR | | 0-0 | 31-31-42 | D00011D | DED | | | D41307J | | GR | | 010-099 |
| 5137B | 24 | H7 | HB | | 2-3 | 31-31-44 | TB0181Y | C118 | BJ | | D00011D | B13 | | | 001-099 |
| 5137R | 24 | H7 | HB | | 0-0 | 31-31-44 | TB0181Y | A118 | BJ | | D00011D | A13 | | | 001-099 |
| 5137Z | | | HB | | 0-0 | 31-31-44 | GD01956 | ST.. | 2 | | D00011D | DED | | | 001-099 |
| 5138B | 24 | H7 | HC | | 2-3 | 31-31-44 | TB0181Y | C117 | BJ | | D00011A | B13 | | | 001-099 |
| 5138R | 24 | H7 | HC | | 0-0 | 31-31-44 | TB0181Y | A117 | BJ | | D00011A | A13 | | | 001-099 |
| 5138Z | | | HC | | 0-0 | 31-31-44 | GD01956 | ST.. | 2 | | D00011A | DED | | | 001-099 |
| 5140B | 24 | G2 | JT | | 4-2 | 31-31-43 | D00011A | F14 | | | D41309J | 29 | | | 001-099 |
| 5140R | 24 | G2 | JT | | 0-0 | 31-31-43 | D00011A | E14 | | | D41309J | 28 | | | 001-099 |
| 5140Z | | | JT | | 0-0 | 31-31-43 | D00011A | DED | | | D41309J | | DR | | 001-099 |
| 5142B | 24 | G2 | HG | | 2-4 | 34-45-01 | D41307J | 42 | | | D00011D | F14 | VP | | 001-002 |
| 5142B | 24 | G2 | HG | | 2-4 | 34-45-01 | D41307J | 42 | | | D00011D | F14 | | | 003-099 |
| 5142B | 24 | G2 | HG | | 6-0 | 34-45-01 | D41307J | 42 | | | D00011A | REF | VP | | 115-199 |
| 5142R | 24 | G2 | HG | | 0-0 | 34-45-01 | D41307J | 41 | | | D00011D | E14 | VP | | 001-002 |
| 5142R | 24 | G2 | HG | | 0-0 | 34-45-01 | D41307J | 41 | | | D00011D | E14 | | | 003-099 |
| 5142R | 24 | G2 | HG | | 0-0 | 34-45-01 | D41307J | 41 | | | D00011A | REF | VP | | 115-199 |
| 5142Z | | | HG | | 0-0 | 34-45-01 | D41307J | | | CZ | D00011D | DED | | | 001-099 |
| 5142Z | | | HG | | 0-0 | 34-45-01 | D41307J | | | CZ | D00011A | DED | | | 115-199 |
| 5146B | 24 | G2 | HA | | 2-7 | 31-31-02 | D00011A | H09 | | | D40255J | 4 | | | 001-099 |
| 5146R | 24 | G2 | HA | | 0-0 | 31-31-02 | D00011A | G09 | | | D40255J | 5 | | | 001-099 |
| 5146Z | | | HA | | 0-0 | 31-31-02 | D00011A | | | DQ | D40255J | 6 | | | 001-099 |
| 5147B | 24 | G2 | HD | | 2-7 | 31-31-02 | D00011A | H11 | | | D40255J | 1 | | | 001-099 |
| 5147R | 24 | G2 | HD | | 0-0 | 31-31-02 | D00011A | G11 | | | D40255J | 2 | | | 001-099 |
| 5147Z | | | HD | | 0-0 | 31-31-02 | D00011A | | | DS | D40255J | 3 | | | 001-099 |
| 5148B | 24 | G2 | HE | | 2-7 | 31-31-02 | D00011D | F15 | | | D40255J | 13 | | | 001-099 |
| 5148R | 24 | G2 | HE | | 0-0 | 31-31-02 | D00011D | E15 | | | D40255J | 14 | | | 001-099 |
| 5148Z | | | HE | | 0-0 | 31-31-02 | D00011D | | | DT | D40255J | 15 | | | 001-099 |
| 8127 | 22 | GA | | | 3-0 | 34-25-12 | D41361J | 11 | | | SM00002 | 9 | | | 002 |
| 8128 | 22 | GA | | | 3-0 | 34-25-12 | D41361J | 12 | | | SM00002 | 9 | | | 002 |
| A-BL | | | | | 0-0 | 31-31-44 | TB0181C | 113 | | | TB0181X | A112 | BJ | | 001-099 |
| A-BL | | | | | 0-0 | 31-31-23 | TB0181C | 113 | | | TB0181X | A112 | BJ | | 115-199 |
| A-RD | | | | | 0-0 | 31-31-44 | TB0181C | 113 | | | TB0181Y | A117 | BJ | | 001-099 |
| A-RD | | | | | 0-0 | 31-31-23 | TB0181C | 113 | | | TB0181Y | A117 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 24

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|--|--|-------------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| A-YL | | | | 0-0 | 31-31-44 | TB0181C | | 113 | | | GD01954 | ST.. | 2 | | 001-099 |
| A-YL | | | | 0-0 | 31-31-23 | TB0181C | | 113 | | | GD01954 | ST.. | 2 | | 115-199 |
| B-BL | | | | 0-0 | 31-31-44 | TB0181C | | 114 | | | TB0181X | B112 | BJ | | 001-099 |
| B-BL | | | | 0-0 | 31-31-23 | TB0181C | | 114 | | | TB0181X | B112 | BJ | | 115-199 |
| B-RD | | | | 0-0 | 31-31-44 | TB0181C | | 114 | | | TB0181Y | C117 | BJ | | 001-099 |
| B-RD | | | | 0-0 | 31-31-23 | TB0181C | | 114 | | | TB0181Y | C117 | BJ | | 115-199 |
| B-YL | | | | 0-0 | 31-31-44 | TB0181C | | 114 | | | GD01954 | ST.. | 2 | | 001-099 |
| B-YL | | | | 0-0 | 31-31-23 | TB0181C | | 114 | | | GD01954 | ST.. | 2 | | 115-199 |
| C-BL | | | | 0-0 | 31-31-44 | TB0181C | | 115 | | | TB0181X | C112 | BJ | | 001-099 |
| C-BL | | | | 0-0 | 31-31-23 | TB0181C | | 115 | | | TB0181X | C112 | BJ | | 115-199 |
| C-RD | | | | 0-0 | 31-31-44 | TB0181C | | 115 | | | TB0181Y | A118 | BJ | | 001-099 |
| C-RD | | | | 0-0 | 31-31-23 | TB0181C | | 115 | | | TB0181Y | A118 | BJ | | 115-199 |
| C-YL | | | | 0-0 | 31-31-44 | TB0181C | | 115 | | | GD01954 | ST.. | 2 | | 001-099 |
| C-YL | | | | 0-0 | 31-31-23 | TB0181C | | 115 | | | GD01954 | ST.. | 2 | | 115-199 |
| D-BL | | | | 0-0 | 31-31-44 | TB0181C | | 116 | | | TB0181X | D112 | BJ | | 001-099 |
| D-BL | | | | 0-0 | 31-31-23 | TB0181C | | 116 | | | TB0181X | D112 | BJ | | 115-199 |
| D-RD | | | | 0-0 | 31-31-44 | TB0181C | | 116 | | | TB0181Y | C118 | BJ | | 001-099 |
| D-RD | | | | 0-0 | 31-31-23 | TB0181C | | 116 | | | TB0181Y | C118 | BJ | | 115-199 |
| D-YL | | | | 0-0 | 31-31-44 | TB0181C | | 116 | | | GD01954 | ST.. | 2 | | 001-099 |
| D-YL | | | | 0-0 | 31-31-23 | TB0181C | | 116 | | | GD01954 | ST.. | 2 | | 115-199 |
| FRAA | | | | 0-0 | 34-53-11 | D41525J | | | AA | | D41525J | 21 | | | 001-099 |
| FRAB | | | | 0-0 | 34-53-11 | D41309J | | | AB | | D41309J | 24 | | | ALL |
| FRAC | | | | 0-0 | 34-53-11 | D41361J | | | AC | | D41361J | 3 | | | ALL |
| FRAF | | | | 0-0 | 34-55-11 | D42019J | | | AF | | D42019J | 21 | | | ALL |
| FRAG | | | | 0-0 | 34-55-11 | D41309J | | | AG | | D41309J | 44 | | | ALL |
| FRAH | | | | 0-0 | 34-61-12 | D41309J | | | AH | | D41309J | 9 | | | ALL |
| FRAI | | | | 0-0 | 34-22-19 | D41309J | | | AI | | D41309J | 6 | | | ALL |
| FRAJ | | | | 0-0 | 31-31-11 | D41519J | | | AJ | | D41519J | 23 | | | 115-199 |
| FRAK | | | | 0-0 | 31-31-01 | D41519J | | | AK | | D41519J | 27 | | | 001-099 |
| FRAK | | | | 0-0 | 31-31-11 | D41519J | | | AK | | D41519J | 27 | | | 115-199 |
| FRAL | | | | 0-0 | 31-31-11 | D41519J | | | AL | | D41519J | 29 | | | 115-199 |
| FRAN | | | | 0-0 | 31-31-01 | D41521J | | | AN | | D41521J | 9 | | | 001-099 |
| FRAN | | | | 0-0 | 31-31-11 | D41521J | | | AN | | D41521J | 9 | | | 115-199 |
| FRAP | | | | 0-0 | 31-31-41 | D41443J | | | AP | | D41443J | 12 | | | 001-099 |
| FRAP | | | | 0-0 | 31-31-21 | D41443J | | | AP | | D41443J | 12 | | | 115-199 |
| FRAQ | | | | 0-0 | 31-31-41 | D41309J | | | AQ | | D41309J | 51 | | | 001-099 |
| FRAQ | | | | 0-0 | 31-31-21 | D41309J | | | AQ | | D41309J | 51 | | | 115-199 |
| FRAR | | | | 0-0 | 31-31-42 | D41443J | | | AR | | D41443J | 53 | | | 001-099 |
| FRAR | | | | 0-0 | 31-31-21 | D41309J | | | AR | | D41309J | 30 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 25

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | |
| FRAS | | | | 0-0 | 31-31-41 | D41309J | | | AS | D41309J | 27 | | | 001-099 |
| FRAS | | | | 0-0 | 31-31-21 | D41309J | | | AS | D41309J | 27 | | | 115-199 |
| FRAT | | | | 0-0 | 31-31-41 | D41443J | | | AT | D41443J | 20 | | | 001-099 |
| FRAT | | | | 0-0 | 31-31-21 | D41443J | | | AT | D41443J | 20 | | | 115-199 |
| FRAU | | | | 0-0 | 31-31-42 | D41309J | | | AU | D41309J | 55 | | | 001-099 |
| FRAU | | | | 0-0 | 31-31-22 | D41309J | | | AU | D41309J | 55 | | | 115-199 |
| FRAV | | | | 0-0 | 31-31-42 | D41403J | | | AV | D41403J | 3 | | | 001-099 |
| FRAV | | | | 0-0 | 31-31-22 | D41403J | | | AV | D41403J | 3 | | | 115-199 |
| FRAY | | | | 0-0 | 31-31-13 | D41523J | | | AY | D41523J | 16 | | | 115-199 |
| FRAZ | | | | 0-0 | 31-31-13 | D41523J | | | AZ | D41523J | 12 | | | 115-199 |
| FRBA | | | | 0-0 | 31-31-51 | D41956J | | | BA | D41956J | 3 | | | 001-099 |
| FRBA | | | | 0-0 | 31-31-31 | D41956J | | | BA | D41956J | 3 | | | 115-199 |
| FRBB | | | | 0-0 | 31-31-51 | D41956J | | | BB | D41956J | 6 | | | 001-099 |
| FRBB | | | | 0-0 | 31-31-31 | D41956J | | | BB | D41956J | 6 | | | 115-199 |
| FRBC | | | | 0-0 | 31-31-51 | D41956J | | | BC | D41956J | 9 | | | 001-099 |
| FRBC | | | | 0-0 | 31-31-31 | D41956J | | | BC | D41956J | 9 | | | 115-199 |
| FRBD | | | | 0-0 | SPARE | D41361J | | | BD | D41361J | 16 | | | 115-199 |
| FRBE | | | | 0-0 | 31-31-22 | D41307J | | | BE | D41307J | 3 | | | 115-199 |
| FRBF | | | | 0-0 | 31-31-22 | D41307J | | | BF | D41307J | 4 | | | 115-199 |
| FRBG | | | | 0-0 | 31-31-22 | D41361J | | | BG | D41361J | 21 | | | 115-199 |
| FRBH | | | | 0-0 | 31-31-22 | D41361J | | | BH | D41361J | 22 | | | 115-199 |
| FRBI | | | | 0-0 | 31-31-22 | D41361J | | | BI | D41361J | 25 | | | 115-199 |
| FRBJ | | | | 0-0 | 31-31-22 | D41403J | | | BJ | D41403J | 4 | | | 115-199 |
| FRBK | | | | 0-0 | 31-31-22 | D41403J | | | BK | D41403J | 7 | | | 115-199 |
| FRBL | | | | 0-0 | 31-31-22 | D41443J | | | BL | D41443J | 47 | | | 115-199 |
| FRBM | | | | 0-0 | 31-31-22 | D42019J | | | BM | D42019J | 29 | | | 115-199 |
| FRBN | | | | 0-0 | 31-31-22 | D41307J | | | BN | D41307J | 9 | | | 115-199 |
| FRBP | | | | 0-0 | 31-31-22 | D41361J | | | BP | D41361J | 30 | | | 115-199 |
| FRBQ | | | | 0-0 | 31-31-22 | D41403J | | | BQ | D41403J | 12 | | | 115-199 |
| FRBU | | | | 0-0 | 31-31-22 | D41309J | | | BU | D41309J | 33 | | | 115-199 |
| FRBV | | | | 0-0 | 31-31-22 | D41361J | | | BV | D41361J | 10 | | | 115-199 |
| FRBY | | | | 0-0 | 34-45-02 | D41307J | | | BY | D41307J | 47 | | | ALL |
| FRBZ | | | | 0-0 | 34-45-02 | D41307J | | | BZ | D41307J | 54 | | | ALL |
| FRCZ | | | | 0-0 | 34-45-01 | D41307J | | | CZ | D41307J | 43 | | | ALL |
| FRDA | | | | 0-0 | 31-31-42 | D41361J | | | DA | D41361J | 54 | | | 001-099 |
| FRDB | | | | 0-0 | 31-31-42 | D41403J | | | DB | D41403J | 15 | | | 001-099 |
| FRDC | | | | 0-0 | 31-31-42 | D42019J | | | DC | D42019J | 30 | | | 001-099 |
| FRDD | | | | 0-0 | 31-31-42 | D41403J | | | DD | D41403J | 6 | | | 001-099 |
| FRDE | | | | 0-0 | 31-31-43 | D41361J | | | DE | D41361J | 27 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 26

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|--|--|-------------------------------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1433 | 286N1433 | | | E3-3 SHELF BUNDLE (continued) | | | | | | | | | | | |
| FRDF | | | | 0-0 | 31-31-43 | D41361J | | | | | DF | D41361J | 23 | | 001-099 |
| FRDG | | | | 0-0 | 31-31-43 | D41361J | | | | | DG | D41361J | 38 | | 001-099 |
| FRDH | | | | 0-0 | 31-31-43 | D41361J | | | | | DH | D41361J | 19 | | 001-009 |
| FRDI | | | | 0-0 | 31-31-43 | D41403J | | | | | DI | D41403J | 9 | | 001-099 |
| FRDJ | | | | 0-0 | 31-31-43 | D41361J | | | | | DJ | D41361J | 30 | | 001-099 |
| FRDK | | | | 0-0 | 31-31-43 | D41307J | | | | | DK | D41307J | 37 | | 001-099 |
| FRDL | | | | 0-0 | 31-31-43 | D41307J | | | | | DL | D41307J | 33 | | 001-099 |
| FRDM | | | | 0-0 | 31-31-43 | D41307J | | | | | DM | D41307J | 40 | | 001-099 |
| FRDN | | | | 0-0 | 31-31-43 | D41307J | | | | | DN | D41307J | 51 | | 001-099 |
| FRDO | | | | 0-0 | 31-31-43 | D41307J | | | | | DO | D41307J | 9 | | 001-099 |
| FRDP | | | | 0-0 | 31-31-43 | D41403J | | | | | DP | D41403J | 12 | | 001-099 |
| FRDR | | | | 0-0 | 31-31-43 | D41309J | | | | | DR | D41309J | 30 | | 001-099 |
| FRDW | | | | 0-0 | 31-31-41 | D43315J | | | | | DW | D43315J | 3 | | 010-099 |
| FRGR | | | | 0-0 | 31-31-42 | D41307J | | 26 | | | | D41307J | | GR | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W1430

Page 27 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | | 286N1451 | | | | P-51 WIRE BUNDLE | | | | | | | | | |
| 0004 | 24 | GK | | | 2-0 | 31-51-11 | D00121 | 35 | | | SM00020 | | WI | | ALL |
| 0005 | 24 | GK | | | 2-0 | 31-51-11 | D00589 | 35 | | | SM00020 | | WI | | ALL |
| 0009 | 24 | GK | | | 3-0 | 31-51-11 | D00105 | 63 | | | SM00020 | | WI | | ALL |
| 0010 | 24 | GK | | | 1-6 | 31-51-11 | D00113 | 54 | | | SM00020 | | WI | | 001-099 |
| 0010 | 24 | GK | | | 2-0 | 31-51-11 | D00113 | 54 | | | SM00020 | | WI | | 115-199 |
| 0014 | 24 | GK | | | 3-0 | 31-51-11 | D00105 | 65 | | | SM00021 | | WI | | ALL |
| 0015 | 24 | GK | | | 2-0 | 31-51-11 | D00119 | 51 | | | SM00021 | | WI | | ALL |
| 0019 | 24 | GK | | | 2-0 | 31-51-11 | D00117 | 37 | | | SM00021 | | WI | | ALL |
| 0020 | 24 | GK | | | 2-0 | 31-51-11 | D00595 | 51 | | | SM00021 | | WI | | ALL |
| 0032 | 24 | GK | | | 3-0 | 31-51-11 | D00105 | 64 | | | SM00022 | | WI | | ALL |
| 0033 | 24 | GK | | | 2-0 | 31-51-11 | D00115 | 45 | | | SM00022 | | WI | | ALL |
| 0034 | 24 | GK | | | 2-0 | 31-51-11 | D00901 | 45 | | | SM00022 | | WI | | ALL |
| 0035 | 24 | GK | | | 2-0 | 31-51-11 | D00903 | 16 | | | SM00022 | | WI | | ALL |
| 0036 | 22 | GA | | | 4-0 | 31-51-11 | D00105 | 34 | | | D40587J | 24 | | | ALL |
| 0037 | 22 | GA | | | 4-0 | 31-51-11 | D00105 | 33 | | | D40587J | 23 | | | ALL |
| 0039 | 22 | GA | | | 4-0 | 31-51-11 | D40587J | 22 | | | SM00015 | | WI | | ALL |
| 0040 | 24 | GK | | | 3-0 | 31-51-11 | D00105 | 46 | | | SM00015 | | WI | | ALL |
| 0041 | 24 | GK | | | 3-0 | 31-51-11 | D00817 | X1 | | | SM00015 | | WI | | 001-099 |
| 0041 | 24 | GK | | | 4-0 | 31-51-11 | D00817 | X1 | | | SM00015 | | WI | | 115-199 |
| 0042 | 24 | GK | | | 3-0 | 31-51-11 | D00817 | X2 | | | D00105 | 75 | | | ALL |
| 0043 | 24 | GK | | | 3-0 | 31-51-11 | D00817 | A2 | | | SM00005 | | WI | | 001-099 |
| 0043 | 24 | GK | | | 4-0 | 31-51-11 | D00817 | A2 | | | SM00005 | | WI | | 115-199 |
| 0044 | 24 | GK | | | 3-0 | 31-51-11 | D00817 | A3 | | | SM00018 | | WI | | 001-099 |
| 0044 | 24 | GK | | | 4-0 | 31-51-11 | D00817 | A3 | | | SM00018 | | WI | | 115-199 |
| 0045 | 22 | GA | | | 3-0 | 31-51-11 | SM00018 | | WI | | GD01277 | DC.. | 2 | | ALL |
| 0046 | 24 | GK | | | 4-0 | 31-51-11 | D41059J | 26 | | | SM00005 | | WI | | 001-099 |
| 0046 | 24 | GK | | | 3-0 | 31-51-11 | D41059J | 26 | | | SM00005 | | WI | | 115-199 |
| 0050 | 22 | GA | | | 1-0 | 31-51-11 | D00105 | 60 | | | GD00297 | ST.. | 2 | | ALL |
| 0051 | 22 | GA | | | 3-0 | 31-51-11 | D00121 | 14 | | | GD01277 | ST.. | 2 | | ALL |
| 0052 | 22 | GA | | | 3-0 | 31-51-11 | D00121 | 48 | | | GD01277 | DC.. | 2 | | ALL |
| 0054 | 24 | GK | | | 3-0 | 27-32-11 | D00121 | 63 | | | D41059J | 7 | | | ALL |
| 0055 | 24 | GK | | | 3-0 | 27-32-11 | D00121 | 38 | | | D41059J | 8 | | | ALL |
| 0056 | 24 | GK | | | 3-0 | 27-32-11 | D00121 | 4 | | | D41059J | 3 | | | ALL |
| 0057 | 24 | GK | | | 3-0 | 27-32-11 | SM00058 | | WI | | D41059J | 4 | | | ALL |
| 0060 | 24 | GK | | | 3-0 | 27-32-11 | D00121 | 31 | | | D41059J | 1 | | | ALL |
| 0061 | 22 | GA | | | 4-0 | 27-32-11 | GD01277 | DC.. | 2 | | D41059J | 2 | | | 001-099 |
| 0061 | 22 | GA | | | 3-0 | 27-32-11 | GD01277 | DC.. | 2 | | D41059J | 2 | | | 115-199 |
| 0062 | 24 | GK | | | 2-0 | 27-32-11 | D00121 | 40 | | | D41481J | 6 | | | 001-099 |
| 0062 | 24 | GK | | | 3-0 | 27-32-11 | D00121 | 40 | | | D41481J | 6 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 0064 | 24 | | GK | | 3-0 | 27-32-11 | D00121 | | 39 | | D41059J | 27 | | | ALL |
| 0065 | 22 | | GA | | 2-0 | 27-32-11 | D00121 | | 34 | | D41481J | 2 | | | 001-099 |
| 0065 | 22 | | GA | | 3-0 | 27-32-11 | D00121 | | 34 | | D41481J | 2 | | | 115-199 |
| 0068 | 24 | | GK | | 2-0 | 31-51-41 | D00117 | | 20 | | D41481J | 9 | | | 001-099 |
| 0068 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 20 | | D41481J | 9 | | | 115-199 |
| 0069 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | | 38 | | D41481J | 12 | | | ALL |
| 0070 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | | 42 | | SM00047 | | WI | | ALL |
| 0071 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 1 | | SM00008 | | WI | | ALL |
| 0072 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | | 38 | | SM00008 | | WI | | ALL |
| 0073 | 24 | | GK | | 2-0 | 31-51-21 | D41481J | | 20 | | SM00008 | | WI | | 001-099 |
| 0073 | 24 | | GK | | 3-0 | 31-51-21 | D41481J | | 20 | | SM00008 | | WI | | 115-199 |
| 0074 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 37 | | SM00035 | | WI | | 001-008, 010-099 |
| 0075 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 1 | | SM00035 | | WI | | 001-008, 010-099 |
| 0075 | 24 | | GK | | 3-0 | 31-51-31 | D00901 | | 1 | | SM00035 | | WI | | 115-199 |
| 0076 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | | 1 | | SM00035 | | WI | | 001-008, 010-099 |
| 0076 | 24 | | GK | | 3-0 | 31-51-32 | D00115 | | 1 | | SM00035 | | WI | | 115-199 |
| 0077 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 42 | | SM00036 | | WI | | 001-008, 010-099 |
| 0078 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 50 | | SM00036 | | WI | | 001-008, 010-099 |
| 0078 | 24 | | GK | | 3-0 | 31-51-31 | D00901 | | 50 | | SM00036 | | WI | | 115-199 |
| 0079 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | | 50 | | SM00036 | | WI | | 001-008, 010-099 |
| 0079 | 24 | | GK | | 3-0 | 31-51-32 | D00115 | | 50 | | SM00036 | | WI | | 115-199 |
| 0080 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 2 | | SM00012 | | WI | | ALL |
| 0081 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | | 37 | | SM00012 | | WI | | ALL |
| 0082 | 24 | | GK | | 4-0 | 31-51-21 | D41059J | | 31 | | SM00012 | | WI | | 001-099 |
| 0082 | 24 | | GK | | 3-0 | 31-51-21 | D41059J | | 31 | | SM00012 | | WI | | 115-199 |
| 0083 | 24 | | GK | | 3-0 | 31-51-33 | D41059J | | 39 | | D00903 | 41 | | | ALL |
| 0084 | 22 | | GA | | 4-0 | 31-51-31 | D40587J | | 3 | | GD01277 | ST.. | 2 | *3 | ALL |
| 0085 | 24 | | GK | | 4-0 | 22-14-11 | D41059J | | 46 | | SM00035 | | WI | | 001-099 |
| 0086 | 24 | | GK | | 3-0 | 22-14-11 | D41481J | | 28 | | SM00036 | | WI | | 001-099 |
| 0088 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 13 | | SM00040 | | WI | | ALL |
| 0089 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 51 | | SM00041 | | WI | | ALL |
| 0090 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 47 | | SM00044 | | WI | | ALL |
| 0091 | 24 | | GK | | 4-0 | 31-51-31 | D00901 | | 10 | | SM00045 | | WI | | 001-099 |
| 0091 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 10 | | SM00045 | | WI | | 115-199 |
| 0092 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 22 | | D00903 | 23 | | | ALL |
| 0093 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 55 | | D00903 | 47 | | | ALL |
| 0094 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 34 | | D00903 | 51 | | | ALL |
| 0095 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 66 | | D00903 | 57 | | | ALL |
| 0097 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 62 | | SM00042 | | WI | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 0098 | 24 | | GK | | 3-0 | 31-51-31 | SM00042 | | WI | | GD01278 | DC.. | 2 | | 115-199 |
| 0104 | 24 | | GK | | 3-0 | 31-51-12 | D00121 | 1 | | | SM00023 | | WI | | 001-099 |
| 0104 | 24 | | GK | | 2-0 | 31-51-12 | D00121 | 1 | | | SM00023 | | WI | | 115-199 |
| 0105 | 24 | | GK | | 3-0 | 31-51-12 | D00589 | 1 | | | SM00023 | | WI | | 001-099 |
| 0105 | 24 | | GK | | 2-0 | 31-51-12 | D00589 | 1 | | | SM00023 | | WI | | 115-199 |
| 0109 | 24 | | GK | | 3-0 | 31-51-12 | D00107 | 63 | | | SM00023 | | WI | | 001-099 |
| 0109 | 24 | | GK | | 2-0 | 31-51-12 | D00107 | 63 | | | SM00023 | | WI | | 115-199 |
| 0110 | 24 | | GK | | 2-0 | 31-51-12 | D00113 | 21 | | | SM00023 | | WI | | ALL |
| 0114 | 24 | | GK | | 3-0 | 31-51-12 | D00107 | 65 | | | SM00024 | | WI | | ALL |
| 0115 | 24 | | GK | | 2-0 | 31-51-12 | D00119 | 19 | | | SM00024 | | WI | | ALL |
| 0119 | 24 | | GK | | 3-0 | 31-51-12 | D00117 | 3 | | | SM00024 | | WI | | 001-099 |
| 0119 | 24 | | GK | | 2-0 | 31-51-12 | D00117 | 3 | | | SM00024 | | WI | | 115-199 |
| 0120 | 24 | | GK | | 3-0 | 31-51-12 | D00595 | 18 | | | SM00024 | | WI | | 001-099 |
| 0120 | 24 | | GK | | 2-0 | 31-51-12 | D00595 | 18 | | | SM00024 | | WI | | 115-199 |
| 0132 | 24 | | GK | | 3-0 | 31-51-12 | D00107 | 64 | | | SM00025 | | WI | | ALL |
| 0133 | 24 | | GK | | 4-0 | 31-51-12 | D00115 | 56 | | | SM00025 | | WI | | 001-099 |
| 0133 | 24 | | GK | | 2-0 | 31-51-12 | D00115 | 56 | | | SM00025 | | WI | | 115-199 |
| 0134 | 24 | | GK | | 2-0 | 31-51-12 | D00901 | 56 | | | SM00025 | | WI | | ALL |
| 0135 | 24 | | GK | | 2-0 | 31-51-12 | D00903 | 50 | | | SM00025 | | WI | | ALL |
| 0136 | 22 | | GA | | 4-0 | 31-51-12 | D00107 | 34 | | | D40587J | 27 | | | ALL |
| 0137 | 22 | | GA | | 4-0 | 31-51-12 | D00107 | 33 | | | D40587J | 26 | | | ALL |
| 0139 | 22 | | GA | | 4-0 | 31-51-12 | D40587J | 25 | | | SM00016 | | WI | | ALL |
| 0140 | 24 | | GK | | 3-0 | 31-51-12 | D00107 | 46 | | | SM00016 | | WI | | ALL |
| 0141 | 24 | | GK | | 3-0 | 31-51-12 | D00819 | X1 | | | SM00016 | | WI | | 001-099 |
| 0141 | 24 | | GK | | 4-0 | 31-51-12 | D00819 | X1 | | | SM00016 | | WI | | 115-199 |
| 0142 | 24 | | GK | | 3-0 | 31-51-12 | D00819 | X2 | | | D00107 | 75 | | | ALL |
| 0143 | 24 | | GK | | 3-0 | 31-51-12 | D00819 | A2 | | | SM00005 | | WI | | 001-099 |
| 0143 | 24 | | GK | | 4-0 | 31-51-12 | D00819 | A2 | | | SM00005 | | WI | | 115-199 |
| 0144 | 24 | | GK | | 3-0 | 31-51-12 | D00819 | A3 | | | SM00018 | | WI | | 001-099 |
| 0144 | 24 | | GK | | 4-0 | 31-51-12 | D00819 | A3 | | | SM00018 | | WI | | 115-199 |
| 0150 | 22 | | GA | | 1-0 | 31-51-12 | D00107 | 60 | | | GD00298 | ST.. | 2 | | ALL |
| 0151 | 22 | | GA | | 3-0 | 31-51-11 | D00589 | 14 | | | GD00299 | ST.. | 2 | | ALL |
| 0152 | 22 | | GA | | 3-0 | 31-51-11 | D00589 | 48 | | | GD00299 | DC.. | 2 | | ALL |
| 0154 | 24 | | GK | | 3-0 | 27-32-21 | D00589 | 63 | | | D41491J | | 15 | | ALL |
| 0155 | 24 | | GK | | 3-0 | 27-32-21 | D00589 | 38 | | | D41491J | | 16 | | ALL |
| 0156 | 24 | | GK | | 3-0 | 27-32-21 | D00589 | 4 | | | D41491J | | 10 | | ALL |
| 0157 | 24 | | GK | | 3-0 | 27-32-21 | D00589 | 37 | | | D41491J | | 11 | | ALL |
| 0160 | 24 | | GK | | 3-0 | 27-32-21 | D00589 | 31 | | | D41491J | | 8 | | ALL |
| 0161 | 22 | | GA | | 3-0 | 27-32-21 | GD00299 | DC.. | 2 | | D41491J | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 0162 | 24 | | GK | | 3-0 | 27-32-21 | D00589 | 40 | | | D41491J | 4 | | | ALL |
| 0164 | 24 | | GK | | 3-0 | 27-32-21 | D00589 | 39 | | | D41491J | 22 | | | ALL |
| 0165 | 22 | | GA | | 3-0 | 27-32-21 | D00589 | 34 | | | D41491J | 7 | | | ALL |
| 0166 | 24 | | GK | | 3-0 | 31-51-21 | D41481J | 7 | | | SM00083 | | WI | | 001-099 |
| 0167 | 24 | | GK | | 3-0 | 31-51-21 | D41491J | 5 | | | SM00084 | | WI | | 001-099 |
| 0168 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | 53 | | | D41491J | 19 | | | ALL |
| 0169 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | 5 | | | D41491J | 20 | | | ALL |
| 0170 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | 8 | | | SM00048 | | WI | | ALL |
| 0171 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | 35 | | | SM00011 | | WI | | ALL |
| 0172 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | 4 | | | SM00011 | | WI | | ALL |
| 0173 | 24 | | GK | | 3-0 | 31-51-21 | D41491J | 27 | | | SM00011 | | WI | | ALL |
| 0174 | 24 | | GK | | 3-0 | 31-51-41 | D41059J | 44 | | | SM00071 | | WI | | 001-099 |
| 0174 | 24 | | GK | | 4-0 | 31-51-41 | D41059J | 44 | | | SM00071 | | WI | | 115-199 |
| 0175 | 24 | | GK | | 3-0 | 31-51-41 | D41059J | 45 | | | SM00037 | | WI | | ALL |
| 0176 | 24 | | GK | | 3-0 | 31-51-41 | D41481J | 11 | | | SM00037 | | WI | | ALL |
| 0177 | 24 | | GK | | 3-0 | 31-51-41 | D41481J | 10 | | | SM00071 | | WI | | ALL |
| 0178 | 24 | | GK | | 3-0 | 31-51-33 | D41481J | 21 | | | SM00047 | | WI | | ALL |
| 0179 | 24 | | GK | | 3-0 | 31-51-33 | D41481J | 14 | | | SM00047 | | WI | | ALL |
| 0180 | 24 | | GK | | 3-0 | 31-51-33 | D41491J | 28 | | | SM00048 | | WI | | ALL |
| 0181 | 24 | | GK | | 3-0 | 31-51-33 | D41491J | 18 | | | SM00048 | | WI | | ALL |
| 0182 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 19 | | | SM00046 | | WI | | ALL |
| 0183 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 46 | | | SM00043 | | WI | | ALL |
| 0184 | 22 | | GA | | 4-0 | 31-51-32 | D40585J | 3 | | | GD01277 | ST.. | 2 | *4 | 001-099 |
| 0184 | 22 | | GA | | 3-0 | 31-51-32 | D40585J | 3 | | | GD01277 | ST.. | 2 | *4 | 115-199 |
| 0185 | 20 | | GA | | 1-6 | 22-14-11 | D40639J | | | | GD01277 | ST.. | 2 | | ALL |
| 0186 | 20 | | GA | | 1-6 | 22-14-21 | D42081J | | | AD | GD00299 | ST.. | 2 | | ALL |
| 0187 | 24 | | GK | | 1-0 | 34-16-11 | D00119 | 50 | | AE | D00119 | 48 | | | ALL |
| 0188 | 24 | | GK | | 3-0 | 34-16-11 | D00119 | 18 | | | D00119 | 22 | | | 001-099 |
| 0188 | 24 | | GK | | 1-0 | 34-16-11 | D00119 | 18 | | | D00119 | 22 | | | 115-199 |
| 0189 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 51 | | | SM00041 | | WI | | ALL |
| 0190 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 47 | | | SM00044 | | WI | | ALL |
| 0191 | 24 | | GK | | 4-0 | 31-51-32 | D00115 | 10 | | | SM00045 | | WI | | 001-099 |
| 0191 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 10 | | | SM00045 | | WI | | 115-199 |
| 0192 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 22 | | | D00903 | 54 | | | ALL |
| 0193 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 55 | | | D00903 | 13 | | | ALL |
| 0194 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 34 | | | D00903 | 25 | | | ALL |
| 0195 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 66 | | | D00903 | 58 | | | ALL |
| 0196 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | 63 | | | SM00042 | | WI | | 115-199 |
| 0199 | 24 | | GK | | 2-0 | 31-51-42 | D00595 | 9 | | | D00595 | 48 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1451 | 286N1451 | | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | | |
| 0199 | 24 | | GK | | 1-0 | 31-51-42 | D00595 | | 9 | | | D00595 | 48 | | | 115-199 | |
| 0200 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 21 | | | D41059J | 28 | | | ALL | |
| 0201 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 10 | | | SM00071 | | WI | | ALL | |
| 0202 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 9 | | | D41059J | 17 | | | ALL | |
| 0203 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 1 | | | D41059J | 19 | | | ALL | |
| 0204 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 35 | | | D41059J | 18 | | | ALL | |
| 0205 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 2 | | | D41059J | 21 | | | ALL | |
| 0206 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 36 | | | D41059J | 20 | | | ALL | |
| 0207 | 24 | | GK | | 2-0 | 31-51-41 | D00117 | | 43 | | | SM00037 | | WI | | ALL | |
| 0208 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 12 | | | D41491J | 40 | | | ALL | |
| 0209 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 11 | | | SM00070 | | WI | | ALL | |
| 0210 | 24 | | GK | | 3-0 | 31-51-41 | D00117 | | 45 | | | D41059J | 32 | | | ALL | |
| 0211 | 24 | | GK | | 2-0 | 31-51-41 | D00117 | | 6 | | | SM00019 | | WI | | ALL | |
| 0212 | 24 | | GK | | 2-0 | 31-51-41 | D00117 | | 39 | | | SM00044 | | WI | | ALL | |
| 0213 | 24 | | GK | | 2-0 | 34-16-11 | D00119 | | 31 | | | SM00041 | | WI | | ALL | |
| 0214 | 24 | | GK | | 2-0 | 31-51-42 | D00595 | | 52 | | | SM00040 | | WI | | ALL | |
| 0215 | 24 | | GK | | 3-0 | 31-51-42 | D41059J | | 23 | | | SM00038 | | WI | | ALL | |
| 0216 | 24 | | GK | | 2-0 | 31-51-42 | D00595 | | 34 | | | SM00019 | | WI | | ALL | |
| 0217 | 24 | | GK | | 3-0 | 31-51-42 | D40639J | | 14 | | | SM00019 | | WI | | ALL | |
| 0218 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | | 39 | | | D41059J | 29 | | | ALL | |
| 0219 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | | 37 | | | SM00034 | | WI | | 001-099 | |
| 0219 | 24 | | GK | | 2-0 | 31-51-42 | D00595 | | 37 | | | SM00034 | | WI | | 115-199 | |
| 0220 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | | 20 | | | D41059J | 22 | | | ALL | |
| 0221 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | | 40 | | | SM00038 | | WI | | 001-099 | |
| 0221 | 24 | | GK | | 2-0 | 31-51-42 | D00595 | | 40 | | | SM00038 | | WI | | 115-199 | |
| 0222 | 24 | | GK | | 2-0 | 31-51-42 | D00595 | | 22 | | | D00595 | 50 | | | 001-099 | |
| 0222 | 24 | | GK | | 1-0 | 31-51-42 | D00595 | | 22 | | | D00595 | 50 | | | 115-199 | |
| 0223 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | | 3 | | | D41481J | 13 | | | ALL | |
| 0224 | 24 | | GK | | 3-0 | 34-16-11 | D00119 | | 66 | | | D40639J | 10 | | | ALL | |
| 0225 | 24 | | GK | | 3-0 | 34-13-21 | D00119 | | 34 | | | D40639J | 11 | | | ALL | |
| 0226 | 24 | | GK | | 3-0 | 34-16-11 | D00119 | | 6 | | | SM00070 | | WI | | ALL | |
| 0227 | 24 | | GK | | 2-0 | 34-16-11 | D00119 | | 40 | | | SM00038 | | WI | | 001-099 | |
| 0227 | 24 | | GK | | 3-0 | 34-16-11 | D00119 | | 40 | | | D41491J | 13 | | | 115-199 | |
| 0228 | 24 | | GK | | 3-0 | 34-16-11 | D00119 | | 65 | | | D41059J | 25 | | | ALL | |
| 0229 | 24 | | GK | | 3-0 | 34-16-11 | D00119 | | 7 | | | D40639J | 6 | | | ALL | |
| 0230 | 24 | | GK | | 1-0 | 31-51-21 | D00113 | | 16 | | | D00113 | 48 | | | ALL | |
| 0231 | 24 | | GK | | 1-0 | 31-51-21 | D00113 | | 49 | | | D00113 | 55 | | | ALL | |
| 0232 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 43 | | | D00595 | 19 | | | ALL | |
| 0233 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 10 | | | D00117 | 5 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1451 | 286N1451 | | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | | |
| 0234 | 24 | | GK | | 3-0 | 31-51-21 | D00113 | | 34 | | SM00084 | | WI | | 001-099 | | |
| 0234 | 24 | | GK | | 3-0 | 31-51-21 | D00113 | | 34 | | D42081J | 12 | | | 115-199 | | |
| 0235 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 4 | | SM00034 | | WI | | ALL | | |
| 0236 | 24 | | GK | | 4-0 | 31-51-21 | D40639J | | 4 | | SM00034 | | WI | | 001-099 | | |
| 0236 | 24 | | GK | | 3-0 | 31-51-21 | D40639J | | 4 | | SM00034 | | WI | | 115-199 | | |
| 0237 | 24 | | GK | | 3-0 | 31-51-21 | D00113 | | 66 | | SM00083 | | WI | | 001-099 | | |
| 0237 | 24 | | GK | | 3-0 | 31-51-21 | D00113 | | 66 | | D40639J | 5 | | | 115-199 | | |
| 0238 | 24 | | GK | | 3-0 | 31-51-21 | D00113 | | 11 | | D41481J | 15 | | | ALL | | |
| 0239 | 24 | | GK | | 4-0 | 31-51-21 | D00113 | | 8 | | SM00045 | | WI | | 001-099 | | |
| 0239 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 8 | | SM00045 | | WI | | 115-199 | | |
| 0240 | 24 | | GK | | 3-0 | 31-51-21 | D00113 | | 46 | | D41481J | 16 | | | ALL | | |
| 0241 | 24 | | GK | | 3-0 | 31-51-21 | D41481J | | 17 | | SM00039 | | WI | | 001-008, 010-099 | | |
| 0242 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 45 | | SM00039 | | WI | | 001-008, 010-099 | | |
| 0243 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 49 | | SM00039 | | WI | | 001-008, 010-099 | | |
| 0244 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 46 | | SM00043 | | WI | | ALL | | |
| 0245 | 24 | | GK | | 3-0 | 31-51-33 | D00903 | | 21 | | D41059J | 38 | | | ALL | | |
| 0246 | 24 | | GK | | 3-0 | 31-51-31 | D42081J | | 2 | | SM00043 | | WI | | ALL | | |
| 0247 | 24 | | GK | | 3-0 | 31-51-33 | D00903 | | 35 | | D41059J | 15 | | | ALL | | |
| 0248 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 19 | | SM00046 | | WI | | ALL | | |
| 0249 | 24 | | GK | | 3-0 | 31-51-33 | D00903 | | 53 | | D41059J | 14 | | | ALL | | |
| 0250 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | | 6 | | SM00034 | | WI | | ALL | | |
| 0251 | 24 | | GK | | 4-0 | 31-51-31 | D41059J | | 12 | | SM00045 | | WI | | 001-099 | | |
| 0251 | 24 | | GK | | 3-0 | 31-51-31 | D41059J | | 12 | | SM00045 | | WI | | 115-199 | | |
| 0252 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | | 13 | | SM00040 | | WI | | ALL | | |
| 0253 | 24 | | GK | | 3-0 | 23-21-11 | D00903 | | 20 | | D41059J | 30 | | | ALL | | |
| 0254 | 24 | | GK | | 1-0 | 31-51-33 | D00903 | | 31 | | D00903 | 48 | | | ALL | | |
| 0255 | 24 | | GK | | 1-0 | 31-51-33 | D00903 | | 18 | | D00903 | 22 | | | ALL | | |
| 0256 | 24 | | GK | | 3-0 | 31-41-14 | D41059J | | 37 | | SM00046 | | WI | | ALL | | |
| 0260 | 22 | | GA | | 3-0 | 31-51-12 | D00121 | | 15 | | GD01277 | ST.. | 2 | | ALL | | |
| 0261 | 22 | | GA | | 3-0 | 31-51-11 | D00113 | | 14 | | GD00299 | ST.. | 2 | | ALL | | |
| 0262 | 22 | | GA | | 3-0 | 31-51-11 | D00119 | | 14 | | GD00299 | ST.. | 2 | | ALL | | |
| 0263 | 22 | | GA | | 3-0 | 31-51-11 | D00117 | | 14 | | GD00299 | ST.. | 2 | | ALL | | |
| 0264 | 22 | | GA | | 3-0 | 31-51-11 | D00595 | | 14 | | GD00299 | ST.. | 2 | | ALL | | |
| 0265 | 22 | | GA | | 3-0 | 31-51-11 | D00115 | | 14 | | GD00297 | ST.. | 2 | | ALL | | |
| 0266 | 22 | | GA | | 3-0 | 31-51-11 | D00901 | | 14 | | GD00297 | ST.. | 2 | | ALL | | |
| 0267 | 22 | | GA | | 3-0 | 31-51-11 | D00903 | | 14 | | GD00297 | ST.. | 2 | | ALL | | |
| 0268 | 22 | | GA | | 3-0 | 31-51-11 | D00905 | | 14 | | GD01278 | ST.. | 2 | | 009, 115-199 | | |
| 0269 | 22 | | GA | | 3-0 | 31-51-11 | D00815 | | 14 | | GD01278 | ST.. | 2 | | 009, 115-199 | | |
| 0270 | 22 | | GA | | 3-0 | 31-51-11 | D00907 | | 14 | | GD01278 | ST.. | 2 | | 009, 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 0271 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 7 | GD00297 | DC.. | 2 | | ALL |
| 0272 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 8 | GD00297 | DC.. | 2 | | ALL |
| 0273 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 9 | GD00297 | DC.. | 2 | | ALL |
| 0275 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 24 | GD00297 | DC.. | 2 | | ALL |
| 0276 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 25 | GD00297 | DC.. | 2 | | ALL |
| 0277 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 37 | GD00297 | DC.. | 2 | | ALL |
| 0279 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 38 | GD00297 | DC.. | 2 | | ALL |
| 0280 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 57 | GD00297 | DC.. | 2 | | ALL |
| 0281 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 58 | GD00297 | DC.. | 2 | | ALL |
| 0283 | 22 | | GA | | 0-9 | 31-51-11 | D00105 | | | 41 | GD01278 | DC.. | 2 | | 001-099 |
| 0283 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 41 | GD01278 | DC.. | 2 | | 115-199 |
| 0284 | 22 | | GA | | 0-9 | 31-51-11 | D00105 | | | 42 | GD01278 | DC.. | 2 | | 001-099 |
| 0284 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 42 | GD01278 | DC.. | 2 | | 115-199 |
| 0285 | 22 | | GA | | 0-9 | 31-51-11 | D00105 | | | 43 | GD01278 | DC.. | 2 | | 001-099 |
| 0285 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | | 43 | GD01278 | DC.. | 2 | | 115-199 |
| 0290 | 22 | | GA | | 3-0 | 31-51-12 | D00589 | | | 15 | GD00299 | ST.. | 2 | | ALL |
| 0291 | 22 | | GA | | 3-0 | 31-51-12 | D00113 | | | 15 | GD00299 | ST.. | 2 | | ALL |
| 0292 | 22 | | GA | | 3-0 | 31-51-12 | D00119 | | | 15 | GD00299 | ST.. | 2 | | ALL |
| 0293 | 22 | | GA | | 3-0 | 31-51-12 | D00117 | | | 15 | GD00299 | ST.. | 2 | | ALL |
| 0294 | 22 | | GA | | 3-0 | 31-51-12 | D00595 | | | 15 | GD00299 | ST.. | 2 | | ALL |
| 0295 | 22 | | GA | | 3-0 | 31-51-12 | D00115 | | | 15 | GD00298 | ST.. | 2 | | ALL |
| 0296 | 22 | | GA | | 3-0 | 31-51-12 | D00901 | | | 15 | GD00298 | ST.. | 2 | | ALL |
| 0297 | 22 | | GA | | 3-0 | 31-51-12 | D00903 | | | 15 | GD00298 | ST.. | 2 | | ALL |
| 0298 | 22 | | GA | | 3-0 | 31-51-12 | D00905 | | | 15 | GD01279 | ST.. | 2 | | 009, 115-199 |
| 0299 | 22 | | GA | | 3-0 | 31-51-12 | D00815 | | | 15 | GD01279 | ST.. | 2 | | 009, 115-199 |
| 0300 | 22 | | GA | | 3-0 | 31-51-12 | D00907 | | | 15 | GD01279 | ST.. | 2 | | 009, 115-199 |
| 0301 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 7 | GD00298 | DC.. | 2 | | ALL |
| 0302 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 8 | GD00298 | DC.. | 2 | | ALL |
| 0303 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 9 | GD00298 | DC.. | 2 | | ALL |
| 0305 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 24 | GD00298 | DC.. | 2 | | ALL |
| 0306 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 25 | GD00298 | DC.. | 2 | | ALL |
| 0307 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 37 | GD00298 | DC.. | 2 | | ALL |
| 0309 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 38 | GD00298 | DC.. | 2 | | ALL |
| 0310 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 57 | GD00298 | DC.. | 2 | | ALL |
| 0311 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 58 | GD00298 | DC.. | 2 | | ALL |
| 0313 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 41 | GD01279 | DC.. | 2 | | ALL |
| 0314 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 42 | GD01279 | DC.. | 2 | | ALL |
| 0315 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | | 43 | GD01279 | DC.. | 2 | | ALL |
| 0317 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | | 36 | SM00009 | | WI | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------------|----------|---------|-------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1451 | 286N1451 | | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | | |
| 0318 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | | 3 | | | SM00009 | | WI | | ALL | |
| 0319 | 24 | | GK | | 3-0 | 31-51-21 | D41481J | | 19 | | | SM00009 | | WI | | ALL | |
| 0320 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | | 44 | | | SM00010 | | WI | | ALL | |
| 0321 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | | 1 | | | SM00010 | | WI | | ALL | |
| 0322 | 24 | | GK | | 3-0 | 31-51-21 | D41491J | | 26 | | | SM00010 | | WI | | ALL | |
| 0323 | 24 | | GK | | 3-0 | 31-51-33 | D00903 | | 7 | | | D41481J | 29 | | | ALL | |
| 0324 | 24 | | GK | | 4-0 | 31-51-33 | D00903 | | 40 | | | D41491J | 39 | | | 001-099 | |
| 0324 | 24 | | GK | | 3-0 | 31-51-33 | D00903 | | 40 | | | D41491J | 39 | | | 115-199 | |
| 0325 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | | 20 | | | SM00049 | | WI | | 009 | |
| 0326 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | | 20 | | | SM00049 | | WI | | 009 | |
| 0327 | 24 | | GK | | 3-0 | 31-51-34 | D00907 | | 3 | | | D41481J | 8 | | | 009 | |
| 0327 | 24 | | GK | | 3-0 | 31-51-34 | D41481J | | 8 | | | D00907 | 3 | | | 115-199 | |
| 0328 | 24 | | GK | | 3-0 | 31-51-34 | D00907 | | 49 | | | D41059J | 42 | | | 009 | |
| 0328 | 24 | | GK | | 3-0 | 31-51-34 | D41599J | | 4 | | | D00907 | 49 | | | 115-199 | |
| 0329 | 20 | | GA | | 1-6 | 34-16-11 | GD01277 | ST.. | 2 | | | D41481J | | | AW | ALL | |
| 0331 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | 68 | | | GD00297 | DC.. | 2 | | ALL | |
| 0332 | 22 | | GA | | 0-6 | 31-51-11 | D00105 | | 69 | | | GD00297 | DC.. | 2 | | ALL | |
| 0333 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | 68 | | | GD00298 | DC.. | 2 | | ALL | |
| 0334 | 22 | | GA | | 0-6 | 31-51-12 | D00107 | | 69 | | | GD00298 | DC.. | 2 | | ALL | |
| 0335 | 20 | | GA | | 3-0 | 31-51-34 | D41481J | | | | AY | GD01277 | ST.. | 2 | | 009 | |
| 0335 | 20 | | GA | | 1-6 | 31-51-34 | D41481J | | | | AY | GD01277 | ST.. | 2 | | 115-199 | |
| 0336 | 20 | | GA | | 1-6 | 31-51-34 | D41059J | | | | AZ | GD01277 | ST.. | 2 | | 009 | |
| 0336 | 20 | | GA | | 1-6 | 31-51-34 | D41599J | | | | AZ | GD01277 | ST.. | 2 | | 115-199 | |
| 0337 | 24 | | GK | | 3-0 | 31-51-34 | D00907 | | 13 | | | D41481J | 36 | | | 009 | |
| 0337 | 24 | | GK | | 3-0 | 31-51-34 | D41481J | | 36 | | | D00907 | 13 | | | 115-199 | |
| 0338 | 24 | | GK | | 3-0 | 31-51-35 | D00901 | | 53 | | | D00905 | 24 | | | 009 | |
| 0338 | 24 | | GK | | 3-0 | 31-51-35 | D00905 | | 24 | | | D00901 | 53 | | | 115-199 | |
| 0345 | 24 | | GK | | 3-0 | 31-51-36 | D00115 | | 53 | | | D00815 | 24 | | | 009 | |
| 0345 | 24 | | GK | | 3-0 | 31-51-36 | D00815 | | 24 | | | D00115 | 53 | | | 115-199 | |
| 0346 | 24 | | GK | | 3-0 | 31-51-34 | D00907 | | 50 | | | SM00049 | | WI | | 009 | |
| 0346 | 24 | | GK | | 3-0 | 31-51-34 | D00907 | | 50 | | | D00907 | CAP | Y | | 115-199 | |
| 0347 | 22 | | GA | | 0-6 | 31-51-11 | M01102 | LOAD | D | | | D00105 | 1 | | | ALL | |
| 0348 | 22 | | GA | | 0-6 | 31-51-11 | M01102 | = GND | D | | | GD00297 | ST.. | 2 | | ALL | |
| 0349 | 22 | | GA | | 0-6 | 31-51-12 | M01103 | LOAD | D | | | D00107 | 1 | | | ALL | |
| 0350 | 22 | | GA | | 0-6 | 31-51-12 | M01103 | = GND | D | | | GD00298 | ST.. | 2 | | ALL | |
| 0351 | 24 | | GK | | 3-0 | 31-51-11 | D00119 | | 27 | | | SM00051 | | WI | | 009 | |
| 0351 | 24 | | GK | | 1-6 | 31-51-11 | D00119 | | 27 | | | SM00051 | | WI | | 115-199 | |
| 0353 | 24 | | GK | | 3-0 | 31-51-11 | D00119 | | 32 | | | SM00053 | | WI | | 009 | |
| 0353 | 24 | | GK | | 1-6 | 31-51-11 | D00119 | | 32 | | | SM00053 | | WI | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|-------------------------------------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | | | | | | | | | | | | | | | |
| | | 286N1451 | | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | |
| 0354 | 24 | GK | | | 1-6 | 31-51-11 | D00905 | 27 | | | SM00051 | | WI | | 009, 115-199 |
| 0355 | 24 | GK | | | 3-0 | 31-51-21 | D40639J | 5 | | | SM00083 | | WI | | 001-099 |
| 0356 | 24 | GK | | | 1-6 | 31-51-11 | D00905 | 32 | | | SM00053 | | WI | | 009, 115-199 |
| 0357 | 24 | GK | | | 3-0 | 31-51-11 | D00905 | 10 | | | SM00021 | | WI | | 009, 115-199 |
| 0358 | 24 | GK | | | 4-0 | 31-51-21 | D42081J | 12 | | | SM00084 | | WI | | 001-099 |
| 0359 | 22 | GA | | | 4-0 | 31-51-31 | D40587J | 31 | | | GD01277 | ST.. | 2 | *3 | ALL |
| 0360 | 22 | GA | | | 4-0 | 31-51-32 | D40585J | 4 | | | GD01277 | ST.. | 2 | *4 | 001-099 |
| 0360 | 22 | GA | | | 3-0 | 31-51-32 | D40585J | 4 | | | GD01277 | ST.. | 2 | *4 | 115-199 |
| 0361 | 24 | GK | | | 3-0 | 31-51-11 | D00105 | 66 | | | SM00057 | | WI | | 009, 115-199 |
| 0362 | 24 | GK | | | 1-6 | 31-51-11 | D00815 | 27 | | | SM00054 | | WI | | 009, 115-199 |
| 0363 | 24 | GK | | | 1-6 | 31-51-11 | D00815 | 32 | | | SM00055 | | WI | | 009, 115-199 |
| 0365 | 24 | GK | | | 3-0 | 31-51-11 | D00815 | 10 | | | SM00057 | | WI | | 009, 115-199 |
| 0366 | 24 | GK | | | 1-6 | 31-51-11 | D00907 | 27 | | | SM00054 | | WI | | 009, 115-199 |
| 0367 | 24 | GK | | | 1-6 | 31-51-11 | D00907 | 32 | | | SM00055 | | WI | | 009, 115-199 |
| 0369 | 24 | GK | | | 3-0 | 31-51-11 | D00907 | 1 | | | SM00057 | | WI | | 009, 115-199 |
| 0371 | 24 | GK | | | 3-0 | 31-51-12 | D00119 | 30 | | | SM00061 | | WI | | 009 |
| 0371 | 24 | GK | | | 1-6 | 31-51-12 | D00119 | 30 | | | SM00061 | | WI | | 115-199 |
| 0373 | 24 | GK | | | 3-0 | 31-51-12 | D00119 | 33 | | | SM00063 | | WI | | 009 |
| 0373 | 24 | GK | | | 1-6 | 31-51-12 | D00119 | 33 | | | SM00063 | | WI | | 115-199 |
| 0374 | 24 | GK | | | 1-6 | 31-51-12 | D00905 | 30 | | | SM00061 | | WI | | 009, 115-199 |
| 0376 | 24 | GK | | | 1-6 | 31-51-12 | D00905 | 33 | | | SM00063 | | WI | | 009, 115-199 |
| 0377 | 24 | GK | | | 3-0 | 31-51-12 | D00905 | 9 | | | SM00024 | | WI | | 009, 115-199 |
| 0379 | 22 | GA | | | 4-0 | 31-51-31 | D41059J | 51 | | | GD01277 | ST.. | 2 | *7 | 001-008, 010-099 |
| 0379 | 22 | GA | | | 4-0 | 31-51-31 | D41059J | 51 | | | GD01277 | ST.. | 2 | *5 | 009 |
| 0380 | 22 | GA | | | 4-0 | 31-51-31 | D41059J | 54 | | | GD01277 | ST.. | 2 | *7 | 001-008, 010-099 |
| 0380 | 22 | GA | | | 4-0 | 31-51-31 | D41059J | 54 | | | GD01277 | ST.. | 2 | *5 | 009 |
| 0381 | 24 | GK | | | 3-0 | 31-51-12 | D00107 | 66 | | | SM00067 | | WI | | 009, 115-199 |
| 0382 | 24 | GK | | | 1-6 | 31-51-12 | D00815 | 30 | | | SM00064 | | WI | | 009, 115-199 |
| 0383 | 24 | GK | | | 1-6 | 31-51-12 | D00815 | 33 | | | SM00065 | | WI | | 009, 115-199 |
| 0385 | 24 | GK | | | 3-0 | 31-51-12 | D00815 | 9 | | | SM00067 | | WI | | 009, 115-199 |
| 0386 | 24 | GK | | | 1-6 | 31-51-12 | D00907 | 30 | | | SM00064 | | WI | | 009, 115-199 |
| 0387 | 24 | GK | | | 1-6 | 31-51-12 | D00907 | 33 | | | SM00065 | | WI | | 009, 115-199 |
| 0389 | 24 | GK | | | 3-0 | 31-51-12 | D00907 | 47 | | | SM00067 | | WI | | 009, 115-199 |
| 0390 | 24 | GK | | | 1-0 | 31-51-34 | D00907 | 6 | | | D00907 | 48 | | | 009, 115-199 |
| 0391 | 24 | GK | | | 1-0 | 31-51-34 | D00907 | 5 | | | D00907 | 22 | | | 009, 115-199 |
| 0392 | 24 | GK | | | 4-0 | 31-51-31 | D00901 | 9 | | | SM00034 | | WI | | 001-099 |
| 0392 | 24 | GK | | | 3-0 | 31-51-31 | D00901 | 9 | | | SM00034 | | WI | | 115-199 |
| 0393 | 24 | GK | | | 4-0 | 31-51-32 | D00115 | 9 | | | SM00034 | | WI | | 001-099 |
| 0393 | 24 | GK | | | 3-0 | 31-51-32 | D00115 | 9 | | | SM00034 | | WI | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 0397 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 62 | | | SM00060 | | WI | | 115-199 |
| 0398 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 63 | | | SM00060 | | WI | | 115-199 |
| 0399 | 24 | | GK | | 3-0 | 31-51-32 | SM00060 | | WI | | GD01279 | DC.. | 2 | | 115-199 |
| 0401 | 24 | | GK | | 2-0 | 31-51-31 | D00901 | 52 | | | SM00069 | | WI | | ALL |
| 0402 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 52 | | | SM00069 | | WI | | ALL |
| 0403 | 24 | | GK | | 3-0 | 31-41-24 | D41491J | 45 | | | SM00069 | | WI | | ALL |
| 0404 | 24 | | GK | | 3-0 | 27-32-11 | D00121 | 37 | | | SM00058 | | WI | | ALL |
| 0405 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | 4 | | | SM00058 | | WI | | ALL |
| 0406 | 24 | | GK | | 3-0 | 31-51-42 | D00595 | 6 | | | D41481J | 26 | | | ALL |
| 0407 | 24 | | GK | | 3-0 | 31-51-21 | D41491J | 33 | | | SM00068 | | WI | | ALL |
| 0408 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | 7 | | | SM00068 | | WI | | ALL |
| 0409 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | 2 | | | SM00068 | | WI | | ALL |
| 0410 | 24 | | GK | | 2-0 | 31-51-33 | D00903 | 36 | | | SM00038 | | WI | | ALL |
| 0411 | 24 | | GK | | 3-0 | 31-51-41 | D41491J | 29 | | | SM00070 | | WI | | ALL |
| 0412 | 24 | | GK | | 3-0 | 31-51-21 | D41491J | 49 | | | SM00059 | | WI | | 001-008, 010-099 |
| 0413 | 24 | | GK | | 2-0 | 31-51-21 | D00113 | 41 | | | SM00059 | | WI | | 001-008, 010-099 |
| 0414 | 24 | | GK | | 2-0 | 31-51-32 | D00115 | 49 | | | SM00059 | | WI | | 001-008, 010-099 |
| 0415 | 24 | | GK | | 3-0 | 34-16-11 | D41491J | 12 | | | SM00038 | | WI | | 115-199 |
| 0416 | 24 | | GK | | 3-0 | 31-51-43 | D00595 | 10 | | | D40639J | 13 | | | ALL |
| 0417 | 24 | | GK | | 3-0 | 31-51-43 | D00595 | 13 | | | D41059J | 33 | | | ALL |
| 0418 | 22 | | GA | | 3-0 | 31-51-43 | D00595 | 41 | | | D41481J | 41 | | | ALL |
| 0419 | 22 | | GA | | 3-0 | 31-51-43 | D41481J | 42 | | | GD01277 | DC.. | 2 | | 001-099 |
| 0419 | 22 | | GA | | 2-0 | 31-51-43 | D41481J | 42 | | | GD01277 | DC.. | 2 | | 115-199 |
| 0420 | 22 | | GA | | 4-0 | 27-32-11 | D41481J | | | BB | GD01277 | ST.. | 2 | *6 | 001-008, 010-099 |
| 0420 | 22 | | GA | | 4-0 | 27-32-11 | D41481J | | | BB | GD01277 | ST.. | 2 | *2 | 009 |
| 0420 | 22 | | GA | | 4-0 | 27-32-11 | D41481J | | | BB | GD01277 | ST.. | 2 | | 115-199 |
| 0421 | 22 | | GA | | 5-0 | 27-32-21 | D41491J | | | BC | GD00299 | ST.. | 2 | *1 | 001-099 |
| 0421 | 22 | | GA | | 5-0 | 27-32-21 | D41491J | | | BC | GD00299 | ST.. | 2 | | 115-199 |
| 0422 | 22 | | GA | | 4-0 | 34-46-12 | D41481J | | | BD | GD01277 | ST.. | 2 | *6 | 001-008, 010-099 |
| 0422 | 22 | | GA | | 4-0 | 34-46-12 | D41481J | | | BD | GD01277 | ST.. | 2 | | 009, 115-199 |
| 0423 | 22 | | GA | | 4-0 | 34-46-12 | D41491J | | | BE | GD00299 | ST.. | 2 | | ALL |
| 0424 | 24 | | GK | | 4-0 | 31-51-21 | D00113 | 6 | | | D41481J | 48 | | | ALL |
| 0425 | 22 | | GA | | 4-0 | 27-32-11 | D41481J | | | BF | GD01277 | ST.. | 2 | *2 | 001-099 |
| 0425 | 22 | | GA | | 4-0 | 27-32-11 | D41481J | | | BF | GD01277 | ST.. | 2 | | 115-199 |
| 0426 | 22 | | GA | | 5-0 | 27-32-21 | D41491J | | | BG | GD00299 | ST.. | 2 | *1 | 001-099 |
| 0426 | 22 | | GA | | 5-0 | 27-32-21 | D41491J | | | BG | GD00299 | ST.. | 2 | | 115-199 |
| 0427 | 24 | | GK | | 4-0 | 27-32-12 | D00121 | 56 | | | D00589 | 11 | | | ALL |
| 0428 | 24 | | GK | | 4-0 | 27-32-12 | D00121 | 11 | | | D00589 | 56 | | | ALL |
| 0429 | 22 | | GA | | 3-0 | 27-32-12 | D00121 | 44 | | | GD01278 | DC.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 0430 | 22 | GA | | | 3-0 | 27-32-12 | D00121 | | | | GD01278 | DC.. | 2 | | ALL |
| 0431 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 4 | | ALL |
| 0432 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 5 | | ALL |
| 0433 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 6 | | ALL |
| 0434 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 7 | | ALL |
| 0435 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 8 | | ALL |
| 0436 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 9 | | ALL |
| 0437 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 10 | | ALL |
| 0438 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 11 | | ALL |
| 0439 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D40587J | | 12 | | ALL |
| 0440 | 24 | GK | | | 4-0 | 27-32-12 | D00121 | | | | D00817 | | A1 | | ALL |
| 0441 | 22 | GA | | | 3-0 | 27-32-22 | D00589 | | | | GD01279 | DC.. | 2 | | ALL |
| 0442 | 22 | GA | | | 3-0 | 27-32-22 | D00589 | | | | GD01279 | DC.. | 2 | | ALL |
| 0443 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 13 | | ALL |
| 0444 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 14 | | ALL |
| 0445 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 15 | | ALL |
| 0446 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 16 | | ALL |
| 0447 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 17 | | ALL |
| 0448 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 18 | | ALL |
| 0449 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 19 | | ALL |
| 0450 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 20 | | ALL |
| 0451 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D40587J | | 21 | | ALL |
| 0452 | 24 | GK | | | 4-0 | 27-32-22 | D00589 | | | | D00819 | | A1 | | ALL |
| 0453 | 22 | GA | | | 5-0 | 31-51-11 | D40587J | | | | GD01278 | DC.. | 2 | | ALL |
| 0454 | 22 | GA | | | 5-0 | 31-51-12 | D40587J | | | | GD01279 | DC.. | 2 | | ALL |
| 0459 | 22 | GA | | | 4-0 | 27-32-12 | D00121 | | | | GD01278 | DC.. | 2 | | 001-008, 010-099 |
| 0460 | 22 | GA | | | 4-0 | 27-32-12 | D00121 | | | | GD01278 | DC.. | 2 | | 001-008, 010-099 |
| 0461 | 22 | GA | | | 3-0 | 27-32-22 | D00589 | | | | GD01279 | DC.. | 2 | | 001-008, 010-099 |
| 0462 | 22 | GA | | | 3-0 | 27-32-22 | D00589 | | | | GD01279 | DC.. | 2 | | 001-008, 010-099 |
| 0463 | 22 | GA | | | 4-0 | 27-32-11 | D41481J | | | BM | GD01277 | ST.. | 2 | *2 | 001-099 |
| 0464 | 22 | GA | | | 5-0 | 27-32-21 | D41491J | | | BN | GD00299 | ST.. | 2 | *1 | 001-099 |
| 0465 | 24 | GK | | | 2-0 | 27-32-11 | D00121 | | | | SM00038 | | WI | | 001-099 |
| 0466 | 24 | GK | | | 2-0 | 27-32-21 | D00589 | | | | SM00038 | | WI | | 001-099 |
| 1001 | 22 | CN | BY | | 4-0 | 31-51-11 | D40714J | | | | M01102 | LINE | D | | ALL |
| 1001Z | | | BY | | 0-0 | 31-51-11 | D40714J | | DED | | GD01278 | ST.. | 2 | | ALL |
| 1002 | 22 | CN | BZ | | 4-0 | 31-51-11 | D40714J | | | | D00105 | | 4 | | ALL |
| 1002Z | | | BZ | | 0-0 | 31-51-11 | D40714J | | DED | | D00105 | | 59 | | ALL |
| 1003 | 24 | CN | BA | | 2-0 | 31-51-11 | D00105 | | | | D00121 | | 27 | | 001-099 |
| 1003 | 24 | CN | BA | | 3-0 | 31-51-11 | D00105 | | | | D00121 | | 27 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------------|----------|--------|------|------|--------|-------|---------|------|--------|------------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W1451 | 286N1451 | | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | | |
| 1003Z | | | | BA | 0-0 | 31-51-11 | D00105 | | | | AF | D00121 | DED | | ALL | | |
| 1004 | 24 | | CN | BB | 2-0 | 31-51-11 | D00105 | 20 | | | | D00121 | 17 | | 001-099 | | |
| 1004 | 24 | | CN | BB | 3-0 | 31-51-11 | D00105 | 20 | | | | D00121 | 17 | | 115-199 | | |
| 1004Z | | | | BB | 0-0 | 31-51-11 | D00105 | | | | AF | D00121 | DED | | ALL | | |
| 1005 | 24 | | CN | BC | 2-0 | 31-51-11 | D00105 | 15 | | | | D00121 | 32 | | 001-099 | | |
| 1005 | 24 | | CN | BC | 3-0 | 31-51-11 | D00105 | 15 | | | | D00121 | 32 | | 115-199 | | |
| 1005Z | | | | BC | 0-0 | 31-51-11 | D00105 | | | | AF | D00121 | DED | | ALL | | |
| 1006 | 24 | | CN | BD | 2-0 | 31-51-11 | D00105 | 11 | | | | D00589 | 27 | | 001-099 | | |
| 1006 | 24 | | CN | BD | 3-0 | 31-51-11 | D00105 | 11 | | | | D00589 | 27 | | 115-199 | | |
| 1006Z | | | | BD | 0-0 | 31-51-11 | D00105 | | | | AG | D00589 | DED | | ALL | | |
| 1007 | 24 | | CN | BE | 2-0 | 31-51-11 | D00105 | 21 | | | | D00589 | 17 | | 001-099 | | |
| 1007 | 24 | | CN | BE | 3-0 | 31-51-11 | D00105 | 21 | | | | D00589 | 17 | | 115-199 | | |
| 1007Z | | | | BE | 0-0 | 31-51-11 | D00105 | | | | AG | D00589 | DED | | ALL | | |
| 1008 | 24 | | CN | BF | 2-0 | 31-51-11 | D00105 | 16 | | | | D00589 | 32 | | 001-099 | | |
| 1008 | 24 | | CN | BF | 3-0 | 31-51-11 | D00105 | 16 | | | | D00589 | 32 | | 115-199 | | |
| 1008Z | | | | BF | 0-0 | 31-51-11 | D00105 | | | | AG | D00589 | DED | | ALL | | |
| 1009 | 24 | | CN | BG | 2-0 | 31-51-11 | D00105 | 12 | | | | D00113 | 27 | | 001-099 | | |
| 1009 | 24 | | CN | BG | 3-0 | 31-51-11 | D00105 | 12 | | | | D00113 | 27 | | 115-199 | | |
| 1009Z | | | | BG | 0-0 | 31-51-11 | D00105 | | | | AH | D00113 | DED | | ALL | | |
| 1010 | 24 | | CN | BH | 2-0 | 31-51-11 | D00105 | 22 | | | | D00113 | 17 | | 001-099 | | |
| 1010 | 24 | | CN | BH | 3-0 | 31-51-11 | D00105 | 22 | | | | D00113 | 17 | | 115-199 | | |
| 1010Z | | | | BH | 0-0 | 31-51-11 | D00105 | | | | AH | D00113 | DED | | ALL | | |
| 1011 | 24 | | CN | BI | 2-0 | 31-51-11 | D00105 | 17 | | | | D00113 | 32 | | 001-099 | | |
| 1011 | 24 | | CN | BI | 3-0 | 31-51-11 | D00105 | 17 | | | | D00113 | 32 | | 115-199 | | |
| 1011Z | | | | BI | 0-0 | 31-51-11 | D00105 | | | | AH | D00113 | DED | | ALL | | |
| 1012 | 24 | | CN | BJ | 2-0 | 31-51-11 | D00105 | 26 | | | | D00119 | 27 | | 001-008, 010-099 | | |
| 1012 | 24 | | CN | BJ | 2-0 | 31-51-11 | D00105 | 26 | | | | SM00051 | | WI | 009 | | |
| 1012 | 24 | | CN | BJ | 3-0 | 31-51-11 | D00105 | 26 | | | | SM00051 | | WI | 115-199 | | |
| 1012Z | | | | BJ | 0-0 | 31-51-11 | D00105 | | | | AI | D00119 | DED | | 001-008, 010-099 | | |
| 1012Z | | | | BJ | 0-0 | 31-51-11 | D00105 | | | | AI | SM00REF | DED | | 009 | | |
| 1012Z | | | | BJ | 0-0 | 31-51-11 | D00105 | | | | AI | SM00051 | DED | | 115-199 | | |
| 1013 | 24 | | CN | BK | 2-0 | 31-51-11 | D00105 | 35 | | | | D00119 | 17 | | 001-099 | | |
| 1013 | 24 | | CN | BK | 3-0 | 31-51-11 | D00105 | 35 | | | | D00119 | 17 | | 115-199 | | |
| 1013Z | | | | BK | 0-0 | 31-51-11 | D00105 | | | | AI | D00119 | DED | | ALL | | |
| 1014 | 24 | | CN | BL | 2-0 | 31-51-11 | D00105 | 49 | | | | D00119 | 32 | | 001-008, 010-099 | | |
| 1014 | 24 | | CN | BL | 2-0 | 31-51-11 | D00105 | 49 | | | | SM00053 | | WI | 009 | | |
| 1014 | 24 | | CN | BL | 3-0 | 31-51-11 | D00105 | 49 | | | | SM00053 | | WI | 115-199 | | |
| 1014Z | | | | BL | 0-0 | 31-51-11 | D00105 | | | | AI | D00119 | DED | | 001-008, 010-099 | | |
| 1014Z | | | | BL | 0-0 | 31-51-11 | D00105 | | | | AI | SM00REF | DED | | 009 | | |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 1014Z | | | | BL | 0-0 | 31-51-11 | D00105 | | | AI | SM00053 | DED | | | 115-199 |
| 1015 | 24 | CN | | BM | 2-0 | 31-51-11 | D00105 | 13 | | | D00117 | 27 | | | 001-099 |
| 1015 | 24 | CN | | BM | 3-0 | 31-51-11 | D00105 | 13 | | | D00117 | 27 | | | 115-199 |
| 1015Z | | | | BM | 0-0 | 31-51-11 | D00105 | | | AI | D00117 | DED | | | ALL |
| 1016 | 24 | CN | | BN | 2-0 | 31-51-11 | D00105 | 14 | | | D00595 | 27 | | | 001-099 |
| 1016 | 24 | CN | | BN | 3-0 | 31-51-11 | D00105 | 14 | | | D00595 | 27 | | | 115-199 |
| 1016Z | | | | BN | 0-0 | 31-51-11 | D00105 | | | AJ | D00595 | DED | | | ALL |
| 1017 | 24 | CN | | BP | 2-0 | 31-51-11 | D00105 | 23 | | | D00595 | 17 | | | 001-099 |
| 1017 | 24 | CN | | BP | 3-0 | 31-51-11 | D00105 | 23 | | | D00595 | 17 | | | 115-199 |
| 1017Z | | | | BP | 0-0 | 31-51-11 | D00105 | | | AJ | D00595 | DED | | | ALL |
| 1018 | 24 | CN | | BQ | 2-0 | 31-51-11 | D00105 | 48 | | | D00595 | 32 | | | 001-099 |
| 1018 | 24 | CN | | BQ | 3-0 | 31-51-11 | D00105 | 48 | | | D00595 | 32 | | | 115-199 |
| 1018Z | | | | BQ | 0-0 | 31-51-11 | D00105 | | | AJ | D00595 | DED | | | ALL |
| 1019 | 24 | CN | | BR | 2-0 | 31-51-11 | D00105 | 51 | | | D00115 | 27 | | | 001-099 |
| 1019 | 24 | CN | | BR | 3-0 | 31-51-11 | D00105 | 51 | | | D00115 | 27 | | | 115-199 |
| 1019Z | | | | BR | 0-0 | 31-51-11 | D00105 | | | AK | D00115 | DED | | | ALL |
| 1020 | 24 | CN | | BS | 2-0 | 31-51-11 | D00105 | 74 | | | D00115 | 32 | | | 001-099 |
| 1020 | 24 | CN | | BS | 3-0 | 31-51-11 | D00105 | 74 | | | D00115 | 32 | | | 115-199 |
| 1020Z | | | | BS | 0-0 | 31-51-11 | D00105 | | | AK | D00115 | DED | | | ALL |
| 1021 | 24 | CN | | BT | 2-0 | 31-51-11 | D00105 | 47 | | | D00901 | 27 | | | 001-099 |
| 1021 | 24 | CN | | BT | 3-0 | 31-51-11 | D00105 | 47 | | | D00901 | 27 | | | 115-199 |
| 1021Z | | | | BT | 0-0 | 31-51-11 | D00105 | | | AK | D00901 | DED | | | ALL |
| 1022 | 24 | CN | | BU | 2-0 | 31-51-11 | D00105 | 70 | | | D00901 | 32 | | | 001-099 |
| 1022 | 24 | CN | | BU | 3-0 | 31-51-11 | D00105 | 70 | | | D00901 | 32 | | | 115-199 |
| 1022Z | | | | BU | 0-0 | 31-51-11 | D00105 | | | AK | D00901 | DED | | | ALL |
| 1023 | 24 | CN | | BV | 2-0 | 31-51-11 | D00105 | 45 | | | D00903 | 27 | | | 001-099 |
| 1023 | 24 | CN | | BV | 3-0 | 31-51-11 | D00105 | 45 | | | D00903 | 27 | | | 115-199 |
| 1023Z | | | | BV | 0-0 | 31-51-11 | D00105 | | | AL | D00903 | DED | | | ALL |
| 1024 | 24 | CN | | BW | 2-0 | 31-51-11 | D00105 | 50 | | | D00903 | 32 | | | 001-099 |
| 1024 | 24 | CN | | BW | 3-0 | 31-51-11 | D00105 | 50 | | | D00903 | 32 | | | 115-199 |
| 1024Z | | | | BW | 0-0 | 31-51-11 | D00105 | | | AL | D00903 | DED | | | ALL |
| 1025 | 24 | CN | | BX | 2-0 | 31-51-11 | D00105 | 36 | | | D00903 | 17 | | | 001-099 |
| 1025 | 24 | CN | | BX | 3-0 | 31-51-11 | D00105 | 36 | | | D00903 | 17 | | | 115-199 |
| 1025Z | | | | BX | 0-0 | 31-51-11 | D00105 | | | AL | D00903 | DED | | | ALL |
| 1026 | 24 | CN | | DA | 3-0 | 31-51-11 | D00105 | 62 | | | SM00054 | | WI | | 009, 115-199 |
| 1026Z | | | | DA | 0-0 | 31-51-11 | D00105 | | | AU | SM00054 | DED | | | 009, 115-199 |
| 1027 | 24 | CN | | DB | 3-0 | 31-51-11 | D00105 | 76 | | | SM00055 | | WI | | 009, 115-199 |
| 1027Z | | | | DB | 0-0 | 31-51-11 | D00105 | | | AU | SM00055 | DED | | | 009, 115-199 |
| 1028 | 24 | CN | | DC | 3-0 | 31-51-11 | D00105 | 53 | | | D00907 | 17 | | | 009, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 1028Z | | | | DC | 0-0 | 31-51-11 | D00105 | | | AU | D00907 | DED | | | 009, 115-199 |
| 1031 | 22 | CN | CY | | 5-0 | 31-51-12 | D40736J | 3 | | | M01103 | LINE | D | | 001-099 |
| 1031 | 22 | CN | CY | | 4-0 | 31-51-12 | D40736J | 3 | | | M01103 | LINE | D | | 115-199 |
| 1031Z | | | | CY | 0-0 | 31-51-12 | D40736J | DED | | | GD01279 | ST.. | 2 | | ALL |
| 1032 | 22 | CN | CZ | | 5-0 | 31-51-12 | D40736J | 4 | | | D00107 | 4 | | | 001-099 |
| 1032 | 22 | CN | CZ | | 4-0 | 31-51-12 | D40736J | 4 | | | D00107 | 4 | | | 115-199 |
| 1032Z | | | | CZ | 0-0 | 31-51-12 | D40736J | DED | | | D00107 | 59 | | | ALL |
| 1033 | 24 | CN | CA | | 2-0 | 31-51-12 | D00107 | 10 | | | D00121 | 30 | | | 001-099 |
| 1033 | 24 | CN | CA | | 3-0 | 31-51-12 | D00107 | 10 | | | D00121 | 30 | | | 115-199 |
| 1033Z | | | | CA | 0-0 | 31-51-12 | D00107 | | | AM | D00121 | DED | | | ALL |
| 1034 | 24 | CN | CB | | 2-0 | 31-51-12 | D00107 | 20 | | | D00121 | 24 | | | 001-099 |
| 1034 | 24 | CN | CB | | 3-0 | 31-51-12 | D00107 | 20 | | | D00121 | 24 | | | 115-199 |
| 1034Z | | | | CB | 0-0 | 31-51-12 | D00107 | | | AM | D00121 | DED | | | ALL |
| 1035 | 24 | CN | CC | | 2-0 | 31-51-12 | D00107 | 15 | | | D00121 | 33 | | | 001-099 |
| 1035 | 24 | CN | CC | | 3-0 | 31-51-12 | D00107 | 15 | | | D00121 | 33 | | | 115-199 |
| 1035Z | | | | CC | 0-0 | 31-51-12 | D00107 | | | AM | D00121 | DED | | | ALL |
| 1036 | 24 | CN | CD | | 2-0 | 31-51-12 | D00107 | 11 | | | D00589 | 30 | | | 001-099 |
| 1036 | 24 | CN | CD | | 3-0 | 31-51-12 | D00107 | 11 | | | D00589 | 30 | | | 115-199 |
| 1036Z | | | | CD | 0-0 | 31-51-12 | D00107 | | | AN | D00589 | DED | | | ALL |
| 1037 | 24 | CN | CE | | 2-0 | 31-51-12 | D00107 | 21 | | | D00589 | 24 | | | 001-099 |
| 1037 | 24 | CN | CE | | 3-0 | 31-51-12 | D00107 | 21 | | | D00589 | 24 | | | 115-199 |
| 1037Z | | | | CE | 0-0 | 31-51-12 | D00107 | | | AN | D00589 | DED | | | ALL |
| 1038 | 24 | CN | CF | | 2-0 | 31-51-12 | D00107 | 16 | | | D00589 | 33 | | | 001-099 |
| 1038 | 24 | CN | CF | | 3-0 | 31-51-12 | D00107 | 16 | | | D00589 | 33 | | | 115-199 |
| 1038Z | | | | CF | 0-0 | 31-51-12 | D00107 | | | AN | D00589 | DED | | | ALL |
| 1039 | 24 | CN | CG | | 2-0 | 31-51-12 | D00107 | 12 | | | D00113 | 30 | | | 001-099 |
| 1039 | 24 | CN | CG | | 3-0 | 31-51-12 | D00107 | 12 | | | D00113 | 30 | | | 115-199 |
| 1039Z | | | | CG | 0-0 | 31-51-12 | D00107 | | | AP | D00113 | DED | | | ALL |
| 1040 | 24 | CN | CH | | 2-0 | 31-51-12 | D00107 | 22 | | | D00113 | 24 | | | 001-099 |
| 1040 | 24 | CN | CH | | 3-0 | 31-51-12 | D00107 | 22 | | | D00113 | 24 | | | 115-199 |
| 1040Z | | | | CH | 0-0 | 31-51-12 | D00107 | | | AP | D00113 | DED | | | ALL |
| 1041 | 24 | CN | CI | | 2-0 | 31-51-12 | D00107 | 17 | | | D00113 | 33 | | | 001-099 |
| 1041 | 24 | CN | CI | | 3-0 | 31-51-12 | D00107 | 17 | | | D00113 | 33 | | | 115-199 |
| 1041Z | | | | CI | 0-0 | 31-51-12 | D00107 | | | AP | D00113 | DED | | | ALL |
| 1042 | 24 | CN | CJ | | 2-0 | 31-51-12 | D00107 | 26 | | | D00119 | 30 | | | 001-008, 010-099 |
| 1042 | 24 | CN | CJ | | 2-0 | 31-51-12 | D00107 | 26 | | | SM00061 | | WI | | 009 |
| 1042 | 24 | CN | CJ | | 3-0 | 31-51-12 | D00107 | 26 | | | SM00061 | | WI | | 115-199 |
| 1042Z | | | | CJ | 0-0 | 31-51-12 | D00107 | | | AQ | D00119 | DED | | | 001-008, 010-099 |
| 1042Z | | | | CJ | 0-0 | 31-51-12 | D00107 | | | AQ | SM00REF | DED | | | 009 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | | From | | | To | | | Effectivity | |
|------------------------|-------------|----|----|------------------------------|---------|----------|--------|------|------|--------|---------|------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | |
| 1042Z | | | | CJ | 0-0 | 31-51-12 | D00107 | | | AQ | SM00061 | DED | | 115-199 |
| 1043 | 24 | CN | CK | | 2-0 | 31-51-12 | D00107 | 35 | | | D00119 | 24 | | 001-099 |
| 1043 | 24 | CN | CK | | 3-0 | 31-51-12 | D00107 | 35 | | | D00119 | 24 | | 115-199 |
| 1043Z | | | | CK | 0-0 | 31-51-12 | D00107 | | | AQ | D00119 | DED | | ALL |
| 1044 | 24 | CN | CL | | 2-0 | 31-51-12 | D00107 | 49 | | | D00119 | 33 | | 001-008, 010-099 |
| 1044 | 24 | CN | CL | | 2-0 | 31-51-12 | D00107 | 49 | | | SM00063 | | WI | 009 |
| 1044 | 24 | CN | CL | | 3-0 | 31-51-12 | D00107 | 49 | | | SM00063 | | WI | 115-199 |
| 1044Z | | | | CL | 0-0 | 31-51-12 | D00107 | | | AQ | D00119 | DED | | 001-008, 010-099 |
| 1044Z | | | | CL | 0-0 | 31-51-12 | D00107 | | | AQ | SM00REF | DED | | 009 |
| 1044Z | | | | CL | 0-0 | 31-51-12 | D00107 | | | AQ | SM00063 | DED | | 115-199 |
| 1045 | 24 | CN | CM | | 2-0 | 31-51-12 | D00107 | 13 | | | D00117 | 30 | | 001-099 |
| 1045 | 24 | CN | CM | | 3-0 | 31-51-12 | D00107 | 13 | | | D00117 | 30 | | 115-199 |
| 1045Z | | | | CM | 0-0 | 31-51-12 | D00107 | | | AQ | D00117 | DED | | ALL |
| 1046 | 24 | CN | CN | | 2-0 | 31-51-12 | D00107 | 14 | | | D00595 | 30 | | 001-099 |
| 1046 | 24 | CN | CN | | 3-0 | 31-51-12 | D00107 | 14 | | | D00595 | 30 | | 115-199 |
| 1046Z | | | | CN | 0-0 | 31-51-12 | D00107 | | | AR | D00595 | DED | | ALL |
| 1047 | 24 | CN | CP | | 2-0 | 31-51-12 | D00107 | 23 | | | D00595 | 24 | | 001-099 |
| 1047 | 24 | CN | CP | | 3-0 | 31-51-12 | D00107 | 23 | | | D00595 | 24 | | 115-199 |
| 1047Z | | | | CP | 0-0 | 31-51-12 | D00107 | | | AR | D00595 | DED | | ALL |
| 1048 | 24 | CN | CQ | | 2-0 | 31-51-12 | D00107 | 48 | | | D00595 | 33 | | 001-099 |
| 1048 | 24 | CN | CQ | | 3-0 | 31-51-12 | D00107 | 48 | | | D00595 | 33 | | 115-199 |
| 1048Z | | | | CQ | 0-0 | 31-51-12 | D00107 | | | AR | D00595 | DED | | ALL |
| 1049 | 24 | CN | CR | | 2-0 | 31-51-12 | D00107 | 51 | | | D00115 | 30 | | 001-099 |
| 1049 | 24 | CN | CR | | 3-0 | 31-51-12 | D00107 | 51 | | | D00115 | 30 | | 115-199 |
| 1049Z | | | | CR | 0-0 | 31-51-12 | D00107 | | | AS | D00115 | DED | | ALL |
| 1050 | 24 | CN | CS | | 2-0 | 31-51-12 | D00107 | 74 | | | D00115 | 33 | | 001-099 |
| 1050 | 24 | CN | CS | | 3-0 | 31-51-12 | D00107 | 74 | | | D00115 | 33 | | 115-199 |
| 1050Z | | | | CS | 0-0 | 31-51-12 | D00107 | | | AS | D00115 | DED | | ALL |
| 1051 | 24 | CN | CT | | 2-0 | 31-51-12 | D00107 | 47 | | | D00901 | 30 | | 001-099 |
| 1051 | 24 | CN | CT | | 3-0 | 31-51-12 | D00107 | 47 | | | D00901 | 30 | | 115-199 |
| 1051Z | | | | CT | 0-0 | 31-51-12 | D00107 | | | AS | D00901 | DED | | ALL |
| 1052 | 24 | CN | CU | | 2-0 | 31-51-12 | D00107 | 70 | | | D00901 | 33 | | 001-099 |
| 1052 | 24 | CN | CU | | 3-0 | 31-51-12 | D00107 | 70 | | | D00901 | 33 | | 115-199 |
| 1052Z | | | | CU | 0-0 | 31-51-12 | D00107 | | | AS | D00901 | DED | | ALL |
| 1053 | 24 | CN | CV | | 2-0 | 31-51-12 | D00107 | 45 | | | D00903 | 30 | | 001-099 |
| 1053 | 24 | CN | CV | | 3-0 | 31-51-12 | D00107 | 45 | | | D00903 | 30 | | 115-199 |
| 1053Z | | | | CV | 0-0 | 31-51-12 | D00107 | | | AT | D00903 | DED | | ALL |
| 1054 | 24 | CN | CW | | 2-0 | 31-51-12 | D00107 | 50 | | | D00903 | 33 | | 001-099 |
| 1054 | 24 | CN | CW | | 3-0 | 31-51-12 | D00107 | 50 | | | D00903 | 33 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | |
| 1054Z | | | | CW | 0-0 | 31-51-12 | D00107 | | | AT | D00903 | DED | | | ALL |
| 1055 | 24 | CN | CX | | 2-0 | 31-51-12 | D00107 | 36 | | | D00903 | 24 | | | 001-099 |
| 1055 | 24 | CN | CX | | 3-0 | 31-51-12 | D00107 | 36 | | | D00903 | 24 | | | 115-199 |
| 1055Z | | | | CX | 0-0 | 31-51-12 | D00107 | | | AT | D00903 | DED | | | ALL |
| 1056 | 24 | CN | DD | | 2-0 | 31-51-12 | D00107 | 62 | | | SM00064 | | WI | | 009 |
| 1056 | 24 | CN | DD | | 3-0 | 31-51-12 | D00107 | 62 | | | SM00064 | | WI | | 115-199 |
| 1056Z | | | | DD | 0-0 | 31-51-12 | D00107 | | | AV | SM00064 | DED | | | 009, 115-199 |
| 1057 | 24 | CN | DE | | 2-0 | 31-51-12 | D00107 | 76 | | | SM00065 | | WI | | 009 |
| 1057 | 24 | CN | DE | | 3-0 | 31-51-12 | D00107 | 76 | | | SM00065 | | WI | | 115-199 |
| 1057Z | | | | DE | 0-0 | 31-51-12 | D00107 | | | AV | SM00065 | DED | | | 009, 115-199 |
| 1058 | 24 | CN | DF | | 2-0 | 31-51-12 | D00107 | 53 | | | D00907 | 24 | | | 009 |
| 1058 | 24 | CN | DF | | 3-0 | 31-51-12 | D00107 | 53 | | | D00907 | 24 | | | 115-199 |
| 1058Z | | | | DF | 0-0 | 31-51-12 | D00107 | | | AV | D00907 | DED | | | 009, 115-199 |
| 1061 | 24 | CN | DG | | 4-0 | 22-14-11 | D41059J | 46 | | | SM00035 | | WI | | 115-199 |
| 1061Z | | | | DG | 0-0 | 22-14-11 | D41059J | DED | | | SM00035 | DED | | | 115-199 |
| 1062 | 24 | CN | DH | | 4-0 | 22-14-11 | D41481J | 28 | | | SM00036 | | WI | | 115-199 |
| 1062Z | | | | DH | 0-0 | 22-14-11 | D41481J | DED | | | SM00036 | DED | | | 115-199 |
| 1063 | 24 | CN | DI | | 2-0 | 31-51-21 | D00113 | 37 | | | SM00035 | | WI | | 009, 115-199 |
| 1063Z | | | | DI | 0-0 | 31-51-21 | D00113 | DED | | | SM00REF | DED | | | 009 |
| 1063Z | | | | DI | 0-0 | 31-51-21 | D00113 | DED | | | SM00035 | DED | | | 115-199 |
| 1064 | 24 | CN | DJ | | 2-0 | 31-51-21 | D00113 | 42 | | | SM00036 | | WI | | 009, 115-199 |
| 1064Z | | | | DJ | 0-0 | 31-51-21 | D00113 | DED | | | SM00REF | DED | | | 009 |
| 1064Z | | | | DJ | 0-0 | 31-51-21 | D00113 | DED | | | SM00036 | DED | | | 115-199 |
| 1065 | 24 | CN | DK | | 2-0 | 31-51-35 | D00905 | 3 | | | SM00035 | | WI | | 009 |
| 1065Z | | | | DK | 0-0 | 31-51-35 | D00905 | DED | | | SM00REF | DED | | | 009 |
| 1066 | 24 | CN | DL | | 2-0 | 31-51-35 | D00905 | 1 | | | SM00036 | | WI | | 009 |
| 1066Z | | | | DL | 0-0 | 31-51-35 | D00905 | DED | | | SM00REF | DED | | | 009 |
| 1067 | 24 | CN | DM | | 2-0 | 31-51-36 | D00815 | 3 | | | SM00035 | | WI | | 009 |
| 1067Z | | | | DM | 0-0 | 31-51-36 | D00815 | DED | | | SM00REF | DED | | | 009 |
| 1068 | 24 | CN | DN | | 2-0 | 31-51-36 | D00815 | 1 | | | SM00036 | | WI | | 009 |
| 1068Z | | | | DN | 0-0 | 31-51-36 | D00815 | DED | | | SM00REF | DED | | | 009 |
| 1069 | 24 | CN | DP | | 3-0 | 31-51-21 | D41481J | 17 | | | SM00039 | | WI | | 009 |
| 1069 | 24 | CN | DP | | 4-0 | 31-51-21 | SM00039 | | WI | | D41481J | 17 | | | 115-199 |
| 1069Z | | | | DP | 0-0 | 31-51-21 | D41481J | DED | | | SM00039 | DED | | | 009 |
| 1069Z | | | | DP | 0-0 | 31-51-21 | SM00039 | DED | | | D41481J | DED | | | 115-199 |
| 1070 | 24 | CN | DQ | | 3-0 | 31-51-21 | D00113 | 45 | | | SM00039 | | WI | | 009 |
| 1070 | 24 | CN | DQ | | 2-0 | 31-51-21 | D00113 | 45 | | | SM00039 | | WI | | 115-199 |
| 1070Z | | | | DQ | 0-0 | 31-51-21 | D00113 | DED | | | SM00039 | DED | | | 009, 115-199 |
| 1071 | 24 | CN | DR | | 2-0 | 31-51-35 | D00905 | 11 | | | SM00039 | | WI | | 009, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 1071Z | | | | DR | 0-0 | 31-51-35 | D00905 | DED | | | SM00REF | DED | | | 009 |
| 1071Z | | | | DR | 0-0 | 31-51-35 | D00905 | DED | | | SM00039 | DED | | | 115-199 |
| 1072 | 24 | CN | | DS | 3-0 | 31-51-21 | D41491J | 49 | | | SM00059 | | WI | | 009, 115-199 |
| 1072Z | | | | DS | 0-0 | 31-51-21 | D41491J | DED | | | SM00059 | DED | | | 009, 115-199 |
| 1073 | 24 | CN | | DT | 3-0 | 31-51-21 | D00113 | 41 | | | SM00059 | | WI | | 009, 115-199 |
| 1073Z | | | | DT | 0-0 | 31-51-21 | D00113 | DED | | | SM00059 | DED | | | 009, 115-199 |
| 1074 | 24 | CN | | DU | 2-0 | 31-51-36 | D00815 | 12 | | | SM00059 | | WI | | 009, 115-199 |
| 1074Z | | | | DU | 0-0 | 31-51-36 | D00815 | DED | | | SM00REF | DED | | | 009 |
| 1074Z | | | | DU | 0-0 | 31-51-36 | D00815 | DED | | | SM00059 | DED | | | 115-199 |
| 2001B | 24 | 1F | | AR | 4-0 | 31-51-31 | D40587J | 2 | | | D00901 | 24 | | | ALL |
| 2001R | 24 | 1F | | AR | 0-0 | 31-51-31 | D40587J | 1 | | | D00901 | 23 | | | ALL |
| 2002B | 24 | 1F | | AS | 4-0 | 31-51-32 | D40585J | 2 | | | D00115 | 24 | | | ALL |
| 2002R | 24 | 1F | | AS | 0-0 | 31-51-32 | D40585J | 1 | | | D00115 | 23 | | | ALL |
| 2003B | 24 | 1F | | AT | 4-0 | 31-51-31 | D41491J | 35 | | | SM00007 | | WI | | 001-099 |
| 2003B | 24 | 1F | | AT | 3-0 | 31-51-31 | D41491J | 35 | | | SM00007 | | WI | | 115-199 |
| 2003R | 24 | 1F | | AT | 0-0 | 31-51-31 | D41491J | 34 | | | SM00006 | | WI | | ALL |
| 2004B | 24 | 1F | | AU | 4-0 | 31-51-31 | D00901 | 60 | | | SM00007 | | WI | | ALL |
| 2004R | 24 | 1F | | AU | 0-0 | 31-51-31 | D00901 | 28 | | | SM00006 | | WI | | ALL |
| 2005B | 24 | 1F | | AV | 4-0 | 31-51-32 | D00115 | 60 | | | SM00007 | | WI | | 001-099 |
| 2005B | 24 | 1F | | AV | 2-0 | 31-51-32 | D00115 | 60 | | | SM00007 | | WI | | 115-199 |
| 2005R | 24 | 1F | | AV | 0-0 | 31-51-32 | D00115 | 28 | | | SM00006 | | WI | | ALL |
| 2006B | 24 | 1F | | EJ | 4-0 | 31-51-31 | D00901 | 63 | | | SM00086 | | WI | | 001-099 |
| 2006R | 24 | 1F | | EJ | 0-0 | 31-51-31 | D00901 | 62 | | | SM00085 | | WI | | 001-099 |
| 2007B | 24 | 1F | | EF | 4-0 | 31-51-31 | D41059J | 53 | | | SM00086 | | WI | | 001-099 |
| 2007R | 24 | 1F | | EF | 0-0 | 31-51-31 | D41059J | 52 | | | SM00085 | | WI | | 001-099 |
| 2008B | 24 | 1F | | EL | 4-0 | 31-51-32 | D00115 | 63 | | | SM00086 | | WI | | 001-099 |
| 2008R | 24 | 1F | | EL | 0-0 | 31-51-32 | D00115 | 62 | | | SM00085 | | WI | | 001-099 |
| 5001B | 24 | G2 | | AA | 4-0 | 27-32-11 | D00121 | 18 | | | D41481J | 4 | | | ALL |
| 5001R | 24 | G2 | | AA | 0-0 | 27-32-11 | D00121 | 16 | | | D41481J | 3 | | | ALL |
| 5001Z | | | | AA | 0-0 | 27-32-11 | D00121 | DED | | | D41481J | | | BF | ALL |
| 5004B | 24 | G2 | | AD | 3-0 | 34-16-11 | D00119 | 36 | | | D41481J | 31 | | | 001-099 |
| 5004B | 24 | G2 | | AD | 2-0 | 34-16-11 | D00119 | 36 | | | D41481J | 31 | | | 115-199 |
| 5004R | 24 | G2 | | AD | 0-0 | 34-16-11 | D00119 | 2 | | | D41481J | 30 | | | ALL |
| 5004Z | | | | AD | 0-0 | 34-16-11 | D00119 | DED | | | D41481J | | | AW | ALL |
| 5005B | 24 | G2 | | AE | 2-0 | 31-51-33 | D00903 | 45 | | | TB0072Z | 4 | BJ | | 001-099 |
| 5005B | 24 | G2 | | AE | 3-0 | 31-51-33 | D00903 | 45 | | | TB0072Z | 4 | BJ | | 115-199 |
| 5005R | 24 | G2 | | AE | 0-0 | 31-51-33 | D00903 | 11 | | | TB0072Z | 3 | BJ | | ALL |
| 5005Z | | | | AE | 0-0 | 31-51-33 | D00903 | DED | | | TB0072Z | | | BA | ALL |
| 5006B | 24 | G2 | | AF | 3-0 | 22-14-11 | D40639J | 7 | | | D00119 | 35 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 5006R | 24 | G2 | | AF | 0-0 | 22-14-11 | D40639J | 8 | | | D00119 | 1 | | | ALL |
| 5006Z | | | | AF | 0-0 | 22-14-11 | D40639J | | | AD | D00119 | DED | | | ALL |
| 5007B | 24 | G2 | | AG | 3-0 | 31-51-33 | D41491J | 47 | | | TB0072Z | 4 | BJ | | ALL |
| 5007R | 24 | G2 | | AG | 0-0 | 31-51-33 | D41491J | 46 | | | TB0072Z | 3 | BJ | | ALL |
| 5007Z | | | | AG | 0-0 | 31-51-33 | D41491J | 48 | | | TB0072Z | | | BA | ALL |
| 5011B | 24 | G2 | | AH | 4-0 | 27-32-21 | D00589 | 18 | | | D41491J | 2 | | | ALL |
| 5011R | 24 | G2 | | AH | 0-0 | 27-32-21 | D00589 | 16 | | | D41491J | 1 | | | ALL |
| 5011Z | | | | AH | 0-0 | 27-32-21 | D00589 | DED | | | D41491J | | | BG | ALL |
| 5014B | 24 | G2 | | AK | 3-0 | 34-16-11 | D00119 | 38 | | | TB0072Z | 4 | BJ | | 001-099 |
| 5014B | 24 | G2 | | AK | 2-0 | 34-16-11 | D00119 | 38 | | | TB0072Z | 4 | BJ | | 115-199 |
| 5014R | 24 | G2 | | AK | 0-0 | 34-16-11 | D00119 | 4 | | | TB0072Z | 3 | BJ | | ALL |
| 5014Z | | | | AK | 0-0 | 34-16-11 | D00119 | DED | | | TB0072Z | | | BA | ALL |
| 5015B | 24 | G2 | | AL | 3-0 | 31-51-33 | D00903 | 43 | | | TB0072Z | 4 | BJ | | ALL |
| 5015R | 24 | G2 | | AL | 0-0 | 31-51-33 | D00903 | 9 | | | TB0072Z | 3 | BJ | | ALL |
| 5015Z | | | | AL | 0-0 | 31-51-33 | D00903 | DED | | | TB0072Z | | | BA | ALL |
| 5016B | 24 | G2 | | AM | 3-0 | 22-14-21 | D42081J | 10 | | | D00119 | 37 | | | ALL |
| 5016R | 24 | G2 | | AM | 0-0 | 22-14-21 | D42081J | 9 | | | D00119 | 3 | | | ALL |
| 5016Z | | | | AM | 0-0 | 22-14-21 | D42081J | | | AE | D00119 | DED | | | ALL |
| 5017B | 24 | G2 | | AN | 2-0 | 31-51-42 | D00595 | 36 | | | TB0072Z | 6 | BJ | | ALL |
| 5017R | 24 | G2 | | AN | 0-0 | 31-51-42 | D00595 | 2 | | | TB0072Z | 5 | BJ | | ALL |
| 5017Z | | | | AN | 0-0 | 31-51-42 | D00595 | DED | | | TB0072Z | | | AC | ALL |
| 5018B | 24 | G2 | | AO | 2-0 | 31-51-21 | D00113 | 19 | | | TB0072Z | 6 | BJ | | ALL |
| 5018R | 24 | G2 | | AO | 0-0 | 31-51-21 | D00113 | 52 | | | TB0072Z | 5 | BJ | | ALL |
| 5018Z | | | | AO | 0-0 | 31-51-21 | D00113 | DED | | | TB0072Z | | | AC | ALL |
| 5019B | 24 | G2 | | AP | 3-0 | 31-51-21 | D41481J | 38 | | | TB0072Z | 6 | BJ | | ALL |
| 5019R | 24 | G2 | | AP | 0-0 | 31-51-21 | D41481J | 37 | | | TB0072Z | 5 | BJ | | ALL |
| 5019Z | | | | AP | 0-0 | 31-51-21 | D41481J | 39 | | | TB0072Z | | | AC | ALL |
| 5020B | 24 | G2 | | AQ | 3-0 | 31-51-33 | D00903 | 46 | | | TB0072Z | 6 | BJ | | ALL |
| 5020R | 24 | G2 | | AQ | 0-0 | 31-51-33 | D00903 | 12 | | | TB0072Z | 5 | BJ | | ALL |
| 5020Z | | | | AQ | 0-0 | 31-51-33 | D00903 | DED | | | TB0072Z | | | AC | ALL |
| 5021B | 24 | G2 | | AY | 4-0 | 31-51-34 | D00907 | 19 | | | D41481J | 34 | | | 009 |
| 5021B | 24 | G2 | | AY | 4-0 | 31-51-34 | D41481J | 34 | | | D00907 | 19 | | | 115-199 |
| 5021R | 24 | G2 | | AY | 0-0 | 31-51-34 | D00907 | 20 | | | D41481J | 33 | | | 009 |
| 5021R | 24 | G2 | | AY | 0-0 | 31-51-34 | D41481J | 33 | | | D00907 | 20 | | | 115-199 |
| 5021Z | | | | AY | 0-0 | 31-51-34 | D00907 | DED | | | D41481J | | | AY | 009 |
| 5021Z | | | | AY | 0-0 | 31-51-34 | D41481J | | | AY | D00907 | DED | | | 115-199 |
| 5022B | 24 | G2 | | AZ | 4-0 | 31-51-34 | D00907 | 66 | | | D41059J | 48 | | | 009 |
| 5022B | 24 | G2 | | AZ | 4-0 | 31-51-34 | D41599J | 6 | | | D00907 | 66 | | | 115-199 |
| 5022R | 24 | G2 | | AZ | 0-0 | 31-51-34 | D00907 | 34 | | | D41059J | 47 | | | 009 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| 5022R | 24 | G2 | AZ | | 0-0 | 31-51-34 | D41599J | 5 | | | D00907 | 34 | | | 115-199 |
| 5022Z | | | AZ | | 0-0 | 31-51-34 | D00907 | DED | | | D41059J | | AZ | | 009 |
| 5022Z | | | AZ | | 0-0 | 31-51-34 | D41599J | | | AZ | D00907 | DED | | | 115-199 |
| 5023B | 24 | G2 | EA | | 4-0 | 27-32-11 | D00121 | 13 | | | D41481J | 54 | | | ALL |
| 5023R | 24 | G2 | EA | | 0-0 | 27-32-11 | D00121 | 12 | | | D41481J | 53 | | | ALL |
| 5023Z | | | EA | | 0-0 | 27-32-11 | D00121 | DED | | | D41481J | | BB | | ALL |
| 5024B | 24 | G2 | EB | | 4-0 | 27-32-21 | D00589 | 13 | | | D41491J | 43 | | | 001-099 |
| 5024B | 24 | G2 | EB | | 4-0 | 27-32-21 | D00589 | 13 | | | D41491J | 51 | | | 115-199 |
| 5024R | 24 | G2 | EB | | 0-0 | 27-32-21 | D00589 | 12 | | | D41491J | 42 | | | 001-099 |
| 5024R | 24 | G2 | EB | | 0-0 | 27-32-21 | D00589 | 12 | | | D41491J | 50 | | | 115-199 |
| 5024Z | | | EB | | 0-0 | 27-32-21 | D00589 | DED | | | D41491J | | BC | | ALL |
| 5025B | 24 | G2 | EC | | 4-0 | 34-46-12 | D00121 | 54 | | | D41481J | 45 | | | ALL |
| 5025R | 24 | G2 | EC | | 0-0 | 34-46-12 | D00121 | 23 | | | D41481J | 44 | | | ALL |
| 5025Z | | | EC | | 0-0 | 34-46-12 | D00121 | DED | | | D41481J | | BD | | ALL |
| 5026B | 24 | G2 | ED | | 4-0 | 34-46-12 | D00589 | 54 | | | D41491J | 54 | | | ALL |
| 5026R | 24 | G2 | ED | | 0-0 | 34-46-12 | D00589 | 23 | | | D41491J | 53 | | | ALL |
| 5026Z | | | ED | | 0-0 | 34-46-12 | D00589 | DED | | | D41491J | | BE | | ALL |
| 5029B | 24 | G2 | EG | | 4-0 | 27-32-11 | D00121 | 20 | | | D41481J | 51 | | | 001-099 |
| 5029R | 24 | G2 | EG | | 0-0 | 27-32-11 | D00121 | 19 | | | D41481J | 50 | | | 001-099 |
| 5029Z | | | EG | | 0-0 | 27-32-11 | D00121 | DED | | | D41481J | | BM | | 001-099 |
| 5030B | 24 | G2 | EH | | 3-0 | 27-32-21 | D00589 | 20 | | | D41491J | 52 | | | 001-099 |
| 5030R | 24 | G2 | EH | | 0-0 | 27-32-21 | D00589 | 19 | | | D41491J | 51 | | | 001-099 |
| 5030Z | | | EH | | 0-0 | 27-32-21 | D00589 | DED | | | D41491J | | BN | | 001-099 |
| FRAC | | | | | 0-0 | 31-51-21 | GD01277 | ST.. | 2 | *1 | TB0072Z | | AC | | ALL |
| FRAD | | | | | 0-0 | 22-14-11 | D40639J | | | AD | D40639J | 9 | | | ALL |
| FRAE | | | | | 0-0 | 22-14-21 | D42081J | | | AE | D42081J | 11 | | | ALL |
| FRAF | | | | | 0-0 | 31-51-11 | D00105 | | | AF | GD01278 | ST.. | 2 | | 001-008, 010-099 |
| FRAF | | | | | 0-0 | 31-51-11 | D00105 | | | AF | GD01278 | ST.. | 2 | *1 | 009, 115-199 |
| FRAG | | | | | 0-0 | 31-51-11 | D00105 | | | AG | GD01278 | ST.. | 2 | | 001-008, 010-099 |
| FRAG | | | | | 0-0 | 31-51-11 | D00105 | | | AG | GD01278 | ST.. | 2 | *1 | 009, 115-199 |
| FRAH | | | | | 0-0 | 31-51-11 | D00105 | | | AH | GD01278 | ST.. | 2 | | 001-008, 010-099 |
| FRAH | | | | | 0-0 | 31-51-11 | D00105 | | | AH | GD01278 | ST.. | 2 | *2 | 009, 115-199 |
| FRAI | | | | | 0-0 | 31-51-11 | D00105 | | | AI | GD01278 | ST.. | 2 | | 001-008, 010-099 |
| FRAI | | | | | 0-0 | 31-51-11 | D00105 | | | AI | GD01278 | ST.. | 2 | *2 | 009, 115-199 |
| FRAJ | | | | | 0-0 | 31-51-11 | D00105 | | | AJ | GD01278 | ST.. | 2 | | 001-008, 010-099 |
| FRAJ | | | | | 0-0 | 31-51-11 | D00105 | | | AJ | GD01278 | ST.. | 2 | *3 | 009, 115-199 |
| FRAK | | | | | 0-0 | 31-51-11 | D00105 | | | AK | GD01278 | ST.. | 2 | | 001-008, 010-099 |
| FRAK | | | | | 0-0 | 31-51-11 | D00105 | | | AK | GD01278 | ST.. | 2 | *3 | 009, 115-199 |
| FRAL | | | | | 0-0 | 31-51-11 | D00105 | | | AL | GD01278 | ST.. | 2 | | 001-008, 010-099 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|----|------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|------------------|
| | GA | CO | TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| Wire No. | | | | | | | | | | | | | | | | |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | | |
| FRAL | | | | | 0-0 | 31-51-11 | D00105 | | | | AL | GD01278 | ST.. | 2 | *4 | 009, 115-199 |
| FRAM | | | | | 0-0 | 31-51-12 | D00107 | | | | AM | GD01279 | ST.. | 2 | | 001-008, 010-099 |
| FRAM | | | | | 0-0 | 31-51-12 | D00107 | | | | AM | GD01279 | ST.. | 2 | *1 | 009, 115-199 |
| FRAN | | | | | 0-0 | 31-51-12 | D00107 | | | | AN | GD01279 | ST.. | 2 | | 001-008, 010-099 |
| FRAN | | | | | 0-0 | 31-51-12 | D00107 | | | | AN | GD01279 | ST.. | 2 | *1 | 009, 115-199 |
| FRAP | | | | | 0-0 | 31-51-12 | D00107 | | | | AP | GD01279 | ST.. | 2 | | 001-008, 010-099 |
| FRAP | | | | | 0-0 | 31-51-12 | D00107 | | | | AP | GD01279 | ST.. | 2 | *2 | 009, 115-199 |
| FRAQ | | | | | 0-0 | 31-51-12 | D00107 | | | | AQ | GD01279 | ST.. | 2 | | 001-008, 010-099 |
| FRAQ | | | | | 0-0 | 31-51-12 | D00107 | | | | AQ | GD01279 | ST.. | 2 | *2 | 009, 115-199 |
| FRAR | | | | | 0-0 | 31-51-12 | D00107 | | | | AR | GD01279 | ST.. | 2 | | 001-008, 010-099 |
| FRAR | | | | | 0-0 | 31-51-12 | D00107 | | | | AR | GD01279 | ST.. | 2 | *3 | 009, 115-199 |
| FRAS | | | | | 0-0 | 31-51-12 | D00107 | | | | AS | GD01279 | ST.. | 2 | | 001-008, 010-099 |
| FRAS | | | | | 0-0 | 31-51-12 | D00107 | | | | AS | GD01279 | ST.. | 2 | *3 | 009, 115-199 |
| FRAT | | | | | 0-0 | 31-51-12 | D00107 | | | | AT | GD01279 | ST.. | 2 | | 001-008, 010-099 |
| FRAT | | | | | 0-0 | 31-51-12 | D00107 | | | | AT | GD01279 | ST.. | 2 | *4 | 009, 115-199 |
| FRAU | | | | | 0-0 | 31-51-11 | D00105 | | | | AU | GD01278 | ST.. | 2 | *4 | 009, 115-199 |
| FRAV | | | | | 0-0 | 31-51-12 | D00107 | | | | AV | GD01279 | ST.. | 2 | *4 | 009, 115-199 |
| FRAW | | | | | 0-0 | 34-16-11 | D41481J | | 32 | | | D41481J | | | AW | ALL |
| FRAY | | | | | 0-0 | 31-51-34 | D41481J | | | | AY | D41481J | | 35 | | 009, 115-199 |
| FRAZ | | | | | 0-0 | 31-51-34 | D41059J | | | | AZ | D41059J | | 49 | | 009 |
| FRAZ | | | | | 0-0 | 31-51-34 | D41599J | | | | AZ | D41599J | | 7 | | 115-199 |
| FRBA | | | | | 0-0 | 31-51-33 | GD01277 | | ST.. | 2 | *1 | TB0072Z | | | BA | ALL |
| FRBB | | | | | 0-0 | 27-32-11 | D41481J | | 55 | | | D41481J | | | BB | ALL |
| FRBC | | | | | 0-0 | 27-32-21 | D41491J | | 44 | | | D41491J | | | BC | 001-099 |
| FRBC | | | | | 0-0 | 27-32-21 | D41491J | | 52 | | | D41491J | | | BC | 115-199 |
| FRBD | | | | | 0-0 | 34-46-12 | D41481J | | 46 | | | D41481J | | | BD | ALL |
| FRBE | | | | | 0-0 | 34-46-12 | D41491J | | 55 | | | D41491J | | | BE | ALL |
| FRBF | | | | | 0-0 | 27-32-11 | D41481J | | 5 | | | D41481J | | | BF | ALL |
| FRBG | | | | | 0-0 | 27-32-21 | D41491J | | 3 | | | D41491J | | | BG | ALL |
| FRBM | | | | | 0-0 | 27-32-11 | D41481J | | 52 | | | D41481J | | | BM | 001-099 |
| FRBN | | | | | 0-0 | 27-32-21 | D41491J | | 31 | | | D41491J | | | BN | 001-099 |
| PA01 | | | | | 0-0 | 31-51-21 | D00113 | | 47 | | | D00113 | | 63 | | ALL |
| PB01 | | | | | 0-0 | 31-51-32 | D00115 | | 8 | | | D00115 | | 57 | | ALL |
| PC01 | | | | | 0-0 | 31-51-41 | D00117 | | 41 | | | D00117 | | 55 | | ALL |
| PD01 | | | | | 0-0 | 34-16-11 | D00119 | | 43 | | | D00119 | | 60 | | ALL |
| PG01 | | | | | 0-0 | 31-51-42 | D00595 | | 44 | | | D00595 | | 61 | | ALL |
| PH01 | | | | | 0-0 | 31-51-31 | D00901 | | 8 | | | D00901 | | 57 | | ALL |
| PJ01 | | | | | 0-0 | 31-51-33 | D00903 | | 56 | | | D00903 | | 65 | | ALL |
| PK01 | | | | | 0-0 | 31-51-34 | D00907 | | 29 | | | D00907 | | 42 | | 009 |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|--------|------|------|--------|--------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1451 | 286N1451 | | | P-51 WIRE BUNDLE (continued) | | | | | | | | | | | |
| PK01 | | | | | 0-0 | 31-51-34 | D00907 | | 42 | | D00907 | | 29 | | 115-199 |
| PL01 | | | | | 0-0 | 31-51-35 | D00905 | | 7 | | D00905 | | 62 | | 009, 115-199 |
| PM01 | | | | | 0-0 | 31-51-36 | D00815 | | 7 | | D00815 | | 62 | | 009, 115-199 |
| PP01 | | | | | 0-0 | 27-32-11 | D00121 | | 52 | | D00121 | | 65 | | ALL |
| PQ01 | | | | | 0-0 | 27-32-21 | D00589 | | 52 | | D00589 | | 65 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1450

Page 21 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1500 | 286N1500 | | | WING FUELING PANEL | | | | | | | | | | | |
| 0001 | 20 | | GA | | 3-1 | 28-21-11 | S00345 | 2 | C | | D40324P | 17 | | | ALL |
| 0002 | 20 | | GA | | 2-3 | 28-21-21 | S00345 | 3 | C | * | S00347 | 1 | A | * | ALL |
| 0003 | 20 | | GA | | 2-1 | 28-21-21 | S00347 | 2 | A | | D40324P | 15 | | | ALL |
| 0004 | 20 | | GA | | 1-0 | 28-21-21 | S00347 | 1 | A | * | S00416 | 1 | A | | ALL |
| 0006 | 20 | | GA | | 2-2 | 28-21-21 | S00416 | 2 | A | | D40324P | 16 | | | ALL |
| 0007 | 20 | | GA | | 2-3 | 28-21-22 | S00421 | 1 | A | | D40324P | 14 | | | ALL |
| 0008 | 20 | | GA | | 1-2 | 28-21-22 | S00421 | 2 | A | | TB0005P | A006 | 1A | | ALL |
| 0009 | 20 | | GA | | 2-2 | 28-21-22 | S00457 | 1 | A | | D40324P | 13 | | | ALL |
| 0010 | 20 | | GA | | 1-1 | 28-21-22 | S00457 | 2 | A | | TB0005P | A006 | 1A | | ALL |
| 0011 | 20 | | GA | | 2-5 | 28-21-23 | L00083 | 2 | B | | D40326P | 44 | | | ALL |
| 0012 | 20 | | GA | | 1-1 | 28-21-23 | L00083 | 1 | B | | TB0005A | C007 | 1A | | ALL |
| 0013 | 20 | | GA | | 1-1 | 28-21-23 | L00083 | 3 | B | | TB0005B | A002 | 1A | | ALL |
| 0014 | 20 | | GA | | 2-8 | 28-21-23 | L00082 | 2 | B | | D40326P | 46 | | | ALL |
| 0015 | 20 | | GA | | 1-5 | 28-21-23 | L00082 | 1 | B | | TB0005A | C007 | 1A | | ALL |
| 0016 | 20 | | GA | | 1-5 | 28-21-23 | L00082 | 3 | B | | TB0005B | A002 | 1A | | ALL |
| 0017 | 20 | | GA | | 2-8 | 28-21-23 | L00402 | 2 | B | | D40326P | 45 | | | ALL |
| 0018 | 20 | | GA | | 1-5 | 28-21-23 | L00402 | 1 | B | | TB0005A | C007 | 1A | | ALL |
| 0019 | 20 | | GA | | 1-5 | 28-21-23 | L00402 | 3 | B | | TB0005B | A002 | 1A | | ALL |
| 0020 | 20 | | GA | | 2-10 | 28-21-23 | L00081 | 2 | B | | D40326P | 47 | | | ALL |
| 0021 | 20 | | GA | | 1-7 | 28-21-23 | L00081 | 1 | B | | TB0005A | C007 | 1A | | ALL |
| 0022 | 20 | | GA | | 1-7 | 28-21-23 | L00081 | 3 | B | | TB0005B | A002 | 1A | | ALL |
| 0023 | 20 | | GA | | 3-0 | 28-26-11 | L00271 | 2 | B | | D40324P | 5 | | | ALL |
| 0024 | 20 | | GA | | 1-5 | 28-26-11 | L00271 | 1 | B | | S00350 | 2 | C | * | ALL |
| 0025 | 20 | | GA | | 2-5 | 28-26-11 | L00271 | 3 | B | | TB0005B | A002 | 1A | | ALL |
| 0026 | 20 | | GA | | 3-4 | 28-26-11 | L00270 | 2 | B | | D40324P | 3 | | | ALL |
| 0027 | 20 | | GA | | 1-1 | 28-26-11 | L00270 | 1 | B | | S00351 | 2 | C | * | ALL |
| 0028 | 20 | | GA | | 2-8 | 28-26-11 | L00270 | 3 | B | | TB0005B | A002 | 1A | | ALL |
| 0029 | 20 | | GA | | 2-9 | 28-26-11 | S00350 | 3 | C | | D40324P | 6 | | | ALL |
| 0030 | 20 | | GA | | 2-2 | 28-26-11 | S00350 | 2 | C | * | TB0005P | F006 | 1A | | ALL |
| 0031 | 20 | | GA | | 3-4 | 28-26-11 | S00351 | 3 | C | | D40324P | 4 | | | ALL |
| 0032 | 20 | | GA | | 2-9 | 28-26-11 | S00351 | 2 | C | * | TB0005P | F006 | 1A | | ALL |
| 0033 | 20 | | GA | | 2-3 | 28-26-11 | TB0005P | F006 | 1A | | D40324P | 2 | | | ALL |
| 0035 | 20 | | GA | | 2-7 | 28-21-22 | D02624 | 3 | | | D40326P | 31 | | | ALL |
| 0037 | 20 | | GA | | 2-8 | 28-41-11 | SM00023 | | 9 | | D40326P | 36 | | | ALL |
| 0038 | 20 | | GA | | 2-0 | 28-41-11 | D06878 | 12 | | | SM00022 | | 9 | | ALL |
| 0040 | 20 | | GA | | 2-8 | 28-41-11 | SM00024 | | 9 | | D40326P | 34 | | | ALL |
| 0041 | 20 | | GA | | 1-11 | 28-41-11 | D06876 | 12 | | | SM00022 | | 9 | | ALL |
| 0043 | 20 | | GA | | 2-11 | 28-41-11 | SM00025 | | 9 | | D40326P | 35 | | | ALL |
| 0044 | 20 | | GA | | 2-2 | 28-41-11 | D06874 | 12 | | | SM00022 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1500

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1500 | | 286N1500 | | | | WING FUELING PANEL (continued) | | | | | | | | | |
| 0046 | 20 | GA | | | 2-5 | 28-21-22 | S00348 | 3 | C | | D40324P | 7 | | | ALL |
| 0047 | 20 | GA | | | 1-1 | 28-21-22 | S00348 | 2 | C | | TB0005P | D006 | 1A | | ALL |
| 0048 | 20 | GA | | | 1-3 | 28-21-22 | TB0005P | D006 | 1A | | S00417 | 2 | C | | ALL |
| 0049 | 20 | GA | | | 2-7 | 28-21-22 | D40324P | 8 | | | S00417 | 3 | C | | ALL |
| 0050 | 20 | GA | | | 1-7 | 28-21-22 | S00349 | 2 | C | | TB0005P | D006 | 1A | | ALL |
| 0051 | 20 | GA | | | 2-3 | 28-21-22 | TB0005P | D006 | 1A | | D40324P | 20 | | | ALL |
| 0052 | 20 | GA | | | 2-3 | 28-21-22 | TB0005A | A007 | 1A | | D40324P | 22 | | | ALL |
| 0053 | 20 | GA | | | 2-10 | 28-21-22 | S00349 | 3 | C | | D40324P | 9 | | | ALL |
| 0055 | 20 | GA | | | 3-1 | 28-21-11 | S00345 | 3 | C | * | D40324P | 24 | | | ALL |
| 0056 | 20 | GA | | | 2-3 | 28-21-11 | D40326P | 5 | | | TB0005A | C007 | 1A | | ALL |
| 0057 | 20 | GA | | | 2-3 | 28-21-11 | D40326P | 43 | | | TB0005A | C007 | 1A | | ALL |
| 0058 | 20 | GA | | | 2-6 | 28-21-22 | S00418 | 1 | A | | D40324P | 10 | | | ALL |
| 0059 | 20 | GA | | | 1-2 | 28-21-22 | S00418 | 2 | A | | TB0005A | A007 | 1A | | ALL |
| 0060 | 20 | GA | | | 2-9 | 28-21-22 | S00420 | 1 | A | | D40324P | 11 | | | ALL |
| 0061 | 20 | GA | | | 1-5 | 28-21-22 | S00420 | 2 | A | | TB0005A | A007 | 1A | | ALL |
| 0062 | 20 | GA | | | 1-7 | 28-21-22 | S00419 | 2 | A | | TB0005A | A007 | 1A | | ALL |
| 0063 | 20 | GA | | | 2-11 | 28-21-22 | S00419 | 1 | A | | D40324P | 23 | | | ALL |
| 0064 | 20 | GA | | | 2-3 | 28-21-22 | TB0005P | A006 | 1A | | D40324P | 12 | | | ALL |
| 0065 | 20 | GA | | | 1-5 | 28-41-11 | SM00022 | 9 | | | D40326P | 33 | | | ALL |
| 0067 | 20 | GA | | | 2-3 | 28-21-23 | TB0005B | A002 | 1A | | D40326P | 37 | | | ALL |
| 0068 | 20 | GA | | | 1-11 | 28-41-11 | D06876 | 6 | | | SM00006 | 9 | | | ALL |
| 0070 | 20 | GA | | | 2-2 | 28-41-11 | D06874 | 6 | | | SM00006 | 9 | | | ALL |
| 0071 | 20 | GA | | | 2-1 | 28-41-11 | D06876 | 11 | | | TB0005A | A001 | 1A | | ALL |
| 0072 | 20 | GA | | | 2-4 | 28-41-11 | D06874 | 11 | | | TB0005A | A001 | 1A | | ALL |
| 0073 | 20 | GA | | | 2-2 | 28-41-11 | D06878 | 11 | | | TB0005A | A001 | 1A | | ALL |
| 0074 | 20 | GA | | | 2-3 | 28-41-11 | D40326P | 14 | | | TB0005A | A001 | 1A | | ALL |
| 0076 | 20 | GA | | | 2-0 | 28-41-11 | D06878 | 6 | | | SM00006 | 9 | | | ALL |
| 0077 | 20 | GA | | | 2-1 | 28-41-11 | D06876 | 16 | | | TB0005A | C001 | 1A | | ALL |
| 0078 | 20 | GA | | | 2-4 | 28-41-11 | D06874 | 16 | | | TB0005A | C001 | 1A | | ALL |
| 0079 | 20 | GA | | | 2-2 | 28-41-11 | D06878 | 16 | | | TB0005A | C001 | 1A | | ALL |
| 0080 | 20 | GA | | | 2-3 | 28-41-11 | D40326P | 20 | | | TB0005A | C001 | 1A | | ALL |
| 0083 | 20 | GA | | | 1-5 | 28-41-11 | D40326P | 26 | | | SM00006 | 9 | | | ALL |
| 0084 | 20 | GA | | | 0-8 | 28-41-11 | D06876 | 2 | | | SM00007 | 9 | | | ALL |
| 0085 | 20 | GA | | | 0-8 | 28-41-11 | D06876 | 3 | | | SM00007 | 9 | | | ALL |
| 0086 | 20 | GA | | | 0-8 | 28-41-11 | D06876 | 5 | | | SM00007 | 9 | | | ALL |
| 0087 | 20 | GA | | | 0-8 | 28-41-11 | D06876 | 1 | | | SM00008 | 9 | | | ALL |
| 0088 | 20 | GA | | | 0-8 | 28-41-11 | D06876 | 4 | | | SM00008 | 9 | | | ALL |
| 0089 | 20 | GA | | | 0-8 | 28-41-11 | D06876 | 7 | | | SM00008 | 9 | | | ALL |
| 0090 | 20 | GA | | | 0-8 | 28-41-11 | D06874 | 1 | | | SM00009 | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1500

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1500 | 286N1500 | | | WING FUELING PANEL (continued) | | | | | | | | | | | |
| 0091 | 20 | | GA | | 0-8 | 28-41-11 | D06874 | | | | SM00009 | | 9 | | ALL |
| 0092 | 20 | | GA | | 0-8 | 28-41-11 | D06874 | | | | SM00009 | | 9 | | ALL |
| 0093 | 20 | | GA | | 0-8 | 28-41-11 | D06874 | | | | SM00010 | | 9 | | ALL |
| 0094 | 20 | | GA | | 0-8 | 28-41-11 | D06874 | | | | SM00010 | | 9 | | ALL |
| 0095 | 20 | | GA | | 0-8 | 28-41-11 | D06874 | | | | SM00010 | | 9 | | ALL |
| 0096 | 20 | | GA | | 0-7 | 28-41-11 | D06878 | | | | D06878 | 7 | | | ALL |
| 0097 | 20 | | GA | | 0-8 | 28-41-11 | D06878 | | | | SM00011 | | 9 | | ALL |
| 0098 | 20 | | GA | | 0-8 | 28-41-11 | D06878 | | | | SM00011 | | 9 | | ALL |
| 0099 | 20 | | GA | | 0-8 | 28-41-11 | D06878 | | | | SM00011 | | 9 | | ALL |
| 0100 | 20 | | GA | | 0-8 | 28-41-11 | D06878 | | | | SM00011 | | 9 | | ALL |
| 0101 | 20 | | GA | | 2-3 | 28-41-11 | D40326P | | | | TB0005C | F004 | 1A | | ALL |
| 0102 | 20 | | GA | | 2-3 | 28-41-11 | D40326P | | | | TB0005C | A004 | 1A | | ALL |
| 0103 | 20 | | GA | | 0-8 | 28-41-11 | D06876 | | | | SM00024 | | 9 | | ALL |
| 0104 | 20 | | GA | | 0-8 | 28-41-11 | D06874 | | | | SM00025 | | 9 | | ALL |
| 0105 | 20 | | GA | | 0-8 | 28-41-11 | D06878 | | | | SM00023 | | 9 | | ALL |
| 0106 | 20 | | GA | | 0-8 | 28-41-11 | D06878 | | | AA | SM00023 | | 9 | | ALL |
| 0107 | 20 | | GA | | 0-8 | 28-41-11 | D06876 | | | AB | SM00024 | | 9 | | ALL |
| 0108 | 20 | | GA | | 0-8 | 28-41-11 | D06874 | | | AC | SM00025 | | 9 | | ALL |
| 2013B | 20 | | HB | LC | 2-7 | 28-21-22 | D40326P | | | | D02624 | | 1 | | ALL |
| 2013R | 20 | | HB | LC | 0-0 | 28-21-22 | D40326P | | | | D02624 | | 2 | | ALL |
| 2502B | 20 | | GF | AC | 2-2 | 28-41-11 | D06878 | | | | TB0005A | A005 | 1A | | ALL |
| 2502R | 20 | | GF | AC | 0-0 | 28-41-11 | D06878 | | | | TB0005A | C005 | 1A | | ALL |
| 2502Z | | | | AC | 0-0 | 28-41-11 | D06878 | | | AA | TB0005C | F004 | 1A | | ALL |
| 2503B | 20 | | GF | AD | 2-2 | 28-41-11 | D06878 | | | | TB0005A | A003 | 1A | | ALL |
| 2503R | 20 | | GF | AD | 0-0 | 28-41-11 | D06878 | | | | TB0005A | C003 | 1A | | ALL |
| 2503Z | | | | AD | 0-0 | 28-41-11 | D06878 | | | AA | TB0005C | A004 | 1A | | ALL |
| 2505B | 20 | | GF | AF | 2-3 | 28-41-11 | D40326P | | | | TB0005A | A005 | 1A | | ALL |
| 2505R | 20 | | GF | AF | 0-0 | 28-41-11 | D40326P | | | | TB0005A | C005 | 1A | | ALL |
| 2505Z | | | | AF | 0-0 | 28-41-11 | D40326P | | | DED | TB0005C | F004 | 1A | | ALL |
| 2506B | 20 | | GF | GA | 2-1 | 28-41-11 | D06876 | | | | TB0005A | A003 | 1A | | ALL |
| 2506R | 20 | | GF | GA | 0-0 | 28-41-11 | D06876 | | | | TB0005A | C003 | 1A | | ALL |
| 2506Z | | | | GA | 0-0 | 28-41-11 | D06876 | | | AB | TB0005C | A004 | 1A | | ALL |
| 2508B | 20 | | GF | AJ | 2-4 | 28-41-11 | D06874 | | | | TB0005A | A005 | 1A | | ALL |
| 2508R | 20 | | GF | AJ | 0-0 | 28-41-11 | D06874 | | | | TB0005A | C005 | 1A | | ALL |
| 2508Z | | | | AJ | 0-0 | 28-41-11 | D06874 | | | AC | TB0005C | F004 | 1A | | ALL |
| 2509B | 20 | | GF | AK | 2-3 | 28-41-11 | D40326P | | | | TB0005A | A003 | 1A | | ALL |
| 2509R | 20 | | GF | AK | 0-0 | 28-41-11 | D40326P | | | | TB0005A | C003 | 1A | | ALL |
| 2509Z | | | | AK | 0-0 | 28-41-11 | D40326P | | | DED | TB0005C | A004 | 1A | | ALL |
| 2511B | 20 | | GF | DL | 2-1 | 28-41-11 | D06876 | | | | TB0005A | A005 | 1A | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1500

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W1500 | 286N1500 | | | WING FUELING PANEL (continued) | | | | | | | | | | | |
| 2511R | 20 | GF | DL | | 0-0 | 28-41-11 | D06876 | 8 | | | TB0005A | C005 | 1A | | ALL |
| 2511Z | | | DL | | 0-0 | 28-41-11 | D06876 | | | AB | TB0005C | F004 | 1A | | ALL |
| 2512B | 20 | GF | PL | | 2-4 | 28-41-11 | D06874 | 13 | | | TB0005A | A003 | 1A | | ALL |
| 2512R | 20 | GF | PL | | 0-0 | 28-41-11 | D06874 | 14 | | | TB0005A | C003 | 1A | | ALL |
| 2512Z | | | PL | | 0-0 | 28-41-11 | D06874 | | | AC | TB0005C | A004 | 1A | | ALL |
| 3001B | 20 | HC | CN | | 2-7 | 28-21-22 | D40326P | 41 | | | D02624 | | 4 | | ALL |
| 3001R | 20 | HC | CN | | 0-0 | 28-21-22 | D40326P | 39 | | | D02624 | | 6 | | ALL |
| 3001Y | 20 | HC | CN | | 0-0 | 28-21-22 | D40326P | 40 | | | D02624 | | 5 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W1500

Page 4 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | |
|------------|-------------|----|----|-----|--|-------|----------|--------|------|--------|-------|---------|------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice |
| Wire No. | | | | | | | | | | | | | | | |
| W2000 | 286N2000 | | | | MAIN BATTERY TO P6 - POWER FEEDER | | | | | | | | | | |
| 0001 | *1 | | CQ | | 7-0 | | 24-31-11 | D01792 | + | Q | | TB5010 | =1 | F | 001-099 |
| 0001 | *1 | | CQ | | 6-9 | | 24-31-11 | D01792 | + | Q | | TB5010 | =1 | F | 115-199 |
| 0002 | *1 | | CQ | | 3-6 | | 24-31-11 | D01792 | - | Q | | M00224 | A | F | ALL |
| 0003 | *1 | | CQ | | 2-0 | | 24-31-11 | M00224 | B | F | | GD00540 | DC.. | H | 001-099 |
| 0003 | *1 | | CQ | | 2-2 | | 24-31-11 | M00224 | B | F | | GD00540 | DC.. | H | 115-199 |
| W2002 | 286N2002 | | | | P6 TERMINALS TO P11 - BUS PWR - CAT. L | | | | | | | | | | |
| 0001 | 10 | | HA | | 13-0 | | 24-51-13 | TB5013 | 1 | E | | TB5003 | 1 | E | 001-099 |
| 0001 | 08 | | HA | | 12-0 | | 24-51-13 | TB5013 | 1 | E | | TB5003 | 1 | E | 115-199 |
| 0002 | 10 | | HA | | 13-0 | | 24-51-13 | TB5013 | 2 | E | | TB5003 | 2 | E | 001-099 |
| 0002 | 08 | | HA | | 12-0 | | 24-51-13 | TB5013 | 2 | E | | TB5003 | 2 | E | 115-199 |
| 0003 | 10 | | HA | | 13-0 | | 24-51-13 | TB5013 | 3 | E | | TB5003 | 3 | E | 001-099 |
| 0003 | 08 | | HA | | 12-0 | | 24-51-13 | TB5013 | 3 | E | | TB5003 | 3 | E | 115-199 |
| 0004 | 08 | | HA | | 13-0 | | 24-54-11 | TB5011 | 1 | E | | TB5003 | 4 | E | ALL |
| 0005 | 08 | | HA | | 14-0 | | 24-54-11 | TB5011 | 2 | E | | TB5001 | 1 | E | 001-099 |
| 0005 | 08 | | HA | | 16-0 | | 24-54-11 | TB5011 | 2 | E | | TB5001 | 1 | E | 115-199 |
| W2004 | 286N2004 | | | | P6 TERMINALS TO P11 - BUS PWR - CAT.R | | | | | | | | | | |
| 0001 | 08 | | HA | | 10-0 | | 24-51-23 | TB5016 | 1 | E | | TB5004 | 1 | E | 001-099 |
| 0001 | 08 | | HA | | 11-1 | | 24-51-23 | TB5016 | 1 | E | | TB5004 | 1 | E | 115-199 |
| 0002 | 08 | | HA | | 10-0 | | 24-51-23 | TB5016 | 2 | E | | TB5004 | 2 | E | 001-099 |
| 0002 | 08 | | HA | | 10-9 | | 24-51-23 | TB5016 | 2 | E | | TB5004 | 2 | E | 115-199 |
| 0003 | 08 | | HA | | 10-0 | | 24-51-23 | TB5016 | 3 | E | | TB5004 | 3 | E | 001-099 |
| 0003 | 08 | | HA | | 10-8 | | 24-51-23 | TB5016 | 3 | E | | TB5004 | 3 | E | 115-199 |
| 0004 | 08 | | HA | | 11-0 | | 24-54-21 | TB5011 | 4 | E | | TB5004 | 4 | E | 001-099 |
| 0004 | 08 | | HA | | 11-4 | | 24-54-21 | TB5011 | 4 | E | | TB5004 | 4 | E | 115-199 |
| 0005 | 08 | | HA | | 11-0 | | 24-54-21 | TB5011 | 5 | E | | TB5004 | 5 | E | ALL |
| 0006 | 22 | | GA | | 11-0 | | 24-51-72 | TB5016 | 4 | E | | TB5002 | 8 | E | 001-099 |
| 0006 | 22 | | GA | | 14-0 | | 24-51-72 | TB5016 | 4 | E | | TB5002 | 8 | E | 115-199 |
| 0007 | 22 | | GA | | 11-0 | | 24-51-72 | TB5016 | 5 | E | | TB5002 | 9 | E | 001-099 |
| 0007 | 22 | | GA | | 14-0 | | 24-51-72 | TB5016 | 5 | E | | TB5002 | 9 | E | 115-199 |
| 0008 | 22 | | GA | | 11-0 | | 24-51-72 | TB5016 | 6 | E | | TB5002 | 10 | E | 001-099 |
| 0008 | 22 | | GA | | 14-0 | | 24-51-72 | TB5016 | 6 | E | | TB5002 | 10 | E | 115-199 |
| W2008 | 286N2008 | | | | FWD EQUIP AREA TO P6 - BATT CHARGER & INVERTER PWR | | | | | | | | | | |
| 0001 | 06 | | CQ | | 17-11 | | 24-33-11 | M00217 | + | G | | K00104 | A2 | E | ALL |
| 0002 | 06 | | CQ | | 2-11 | | 24-33-11 | M00217 | - | F | | GD00254 | DC.. | G | 001-099 |
| 0002 | 06 | | CQ | | 3-5 | | 24-33-11 | M00217 | - | F | | GD00254 | DC.. | G | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2000

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2008 | 286N2008 | | | FWD EQUIP AREA TO P6 - BATT CHARGER & INVERTER PWR (continued) | | | | | | | | | | | |
| 0003 | 02 | | CQ | | 18-6 | 24-31-11 | M00218 | + | H | | TB5009 | =1 | F | | 001-099 |
| 0003 | 02 | | CQ | | 18-0 | 24-31-11 | M00218 | + | H | | TB5009 | =1 | F | | 115-199 |
| 0004 | 04 | | CQ | | 4-5 | 24-31-11 | M00218 | - | G | | GD00255 | DC.. | G | | 001-099 |
| 0004 | 04 | | CQ | | 4-0 | 24-31-11 | M00218 | - | G | | GD00255 | DC.. | G | | 115-199 |
| 0005 | 14 | | GA | | 21-0 | 24-33-11 | D01672 | 1 | | | TB5013 | 4 | E | | ALL |
| 0006 | 14 | | GA | | 5-0 | 24-33-11 | D01672 | 2 | | | GD00252 | ST.. | E | | ALL |
| 0007 | 14 | | GA | | 5-0 | 24-33-11 | D01672 | 3 | | | GD00253 | AC.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2000

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2010 | 286N2010 | | | P6 DISC. TO P11 - BUS PWR CAT. C | | | | | | | | | | | |
| 0001 | 24 | | GK | | 11-0 | 24-51-31 | D40298P | | 1 | | TB5006 | 1 | E | | ALL |
| 0002 | 22 | | GA | | 11-0 | 24-51-31 | D40298P | | 2 | | TB5006 | 2 | E | | ALL |
| 0003 | 18 | | GA | | 11-0 | 24-51-31 | D40298P | | 3 | | TB5006 | 3 | E | | ALL |
| 0004 | 18 | | GA | | 11-0 | SPARE | D40298P | | 4 | | TB5006 | CAP | Y | | ALL |
| 0005 | 16 | | GA | | 11-0 | SPARE | D40298P | | 5 | | TB5006 | CAP | Y | | ALL |
| W2012 | 286N2012 | | | P6 DISC. TO P11 - BUS PWR CAT. L | | | | | | | | | | | |
| 0001 | 16 | | GA | | 12-0 | 24-51-12 | D40240P | | 1 | | TB5001 | 2 | E | | 001-099 |
| 0001 | 16 | | GA | | 14-0 | 24-51-12 | D40240P | | 1 | | TB5001 | 2 | E | | 115-199 |
| 0002 | 16 | | GA | | 12-0 | 24-51-12 | D40240P | | 2 | | TB5001 | 3 | E | | 001-099 |
| 0002 | 16 | | GA | | 14-0 | 24-51-12 | D40240P | | 2 | | TB5001 | 3 | E | | 115-199 |
| 0003 | 16 | | GA | | 12-0 | 24-51-12 | D40240P | | 3 | | TB5001 | 4 | E | | 001-099 |
| 0003 | 16 | | GA | | 14-0 | 24-51-12 | D40240P | | 3 | | TB5001 | 4 | E | | 115-199 |
| 0004 | 14 | | GA | | 12-0 | 24-53-11 | D40240P | | 4 | | TB5001 | 5 | E | | 001-099 |
| 0004 | 14 | | GA | | 14-0 | 24-53-11 | D40240P | | 4 | | TB5001 | 5 | E | | 115-199 |
| 0005 | 16 | | GA | | 11-0 | 24-51-11 | D40240P | | 5 | | TB5003 | 5 | E | | ALL |
| 0006 | 16 | | GA | | 11-0 | 24-51-11 | D40240P | | 6 | | TB5003 | 6 | E | | ALL |
| 0007 | 16 | | GA | | 11-0 | 24-51-11 | D40240P | | 7 | | TB5003 | 7 | E | | ALL |
| 0016 | 22 | | GA | | 14-0 | 24-51-72 | D42206P | | 6 | | TB5001 | 6 | E | | ALL |
| 0017 | 22 | | GA | | 14-0 | 24-51-72 | D42206P | | 5 | | TB5001 | 7 | E | | ALL |
| 0018 | 22 | | GA | | 14-0 | 24-51-72 | D42206P | | 8 | | TB5001 | 8 | E | | ALL |
| W2013 | 286N2013 | | | AISLE STAND MICROPHONE | | | | | | | | | | | |
| 2001B | 22 | | GB | AA | 44-0 | 23-51-15 | D41220P | | 2 | | D00491 | 2 | | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 23-51-15 | D41220P | | 1 | | D00491 | 1 | | | 115-199 |
| 2501B | 22 | | GU | AB | 44-0 | 23-51-15 | D41220P | | 4 | | D00491 | 4 | | | 115-199 |
| 2501R | 22 | | GU | AB | 0-0 | 23-51-15 | D41220P | | 3 | | D00491 | 3 | | | 115-199 |
| 2501Z | | | | AB | 0-0 | 23-51-15 | D41220P | | 5 | | D00491 | DED | | | 115-199 |
| W2014 | 286N2014 | | | P6 DISC. TO P11 - BUS PWR CAT. R | | | | | | | | | | | |
| 0001 | 16 | | GA | | 10-6 | 24-51-22 | D40248P | | 1 | | TB5002 | 1 | E | | 001-099 |
| 0001 | 16 | | GA | | 12-0 | 24-51-22 | D40248P | | 1 | | TB5002 | 1 | E | | 115-199 |
| 0002 | 16 | | GA | | 10-5 | 24-51-22 | D40248P | | 2 | | TB5002 | 2 | E | | 001-099 |
| 0002 | 16 | | GA | | 12-0 | 24-51-22 | D40248P | | 2 | | TB5002 | 2 | E | | 115-199 |
| 0003 | 16 | | GA | | 10-4 | 24-51-22 | D40248P | | 3 | | TB5002 | 3 | E | | 001-099 |
| 0003 | 16 | | GA | | 12-0 | 24-51-22 | D40248P | | 3 | | TB5002 | 3 | E | | 115-199 |
| 0004 | 16 | | GA | | 9-3 | 24-51-21 | D40248P | | 4 | | TB5004 | 6 | E | | 001-099 |
| 0004 | 16 | | GA | | 9-0 | 24-51-21 | D40248P | | 4 | | TB5004 | 6 | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2010

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|---------|------|------|--------|-------|---------|------|--------|--|---------|-------------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2014 | 286N2014 | | | P6 DISC. TO P11 - BUS PWR CAT. R (continued) | | | | | | | | | | | | | |
| 0005 | 16 | GA | | 9-3 | 24-51-21 | D40248P | | 5 | | | | TB5004 | 7 | E | | 001-099 | |
| 0005 | 16 | GA | | 9-0 | 24-51-21 | D40248P | | 5 | | | | TB5004 | 7 | E | | 115-199 | |
| 0006 | 16 | GA | | 9-4 | 24-51-21 | D40248P | | 6 | | | | TB5004 | 8 | E | | 001-099 | |
| 0006 | 16 | GA | | 9-0 | 24-51-21 | D40248P | | 6 | | | | TB5004 | 8 | E | | 115-199 | |
| 0007 | 12 | GA | | 9-4 | 24-51-52 | D40248P | | 7 | | | | TB5004 | 9 | E | | 001-099 | |
| 0007 | 12 | GA | | 9-0 | 24-51-52 | D40248P | | 7 | | | | TB5004 | 9 | E | | 115-199 | |
| 0008 | 12 | GA | | 9-5 | 24-51-52 | D40248P | | 8 | | | | TB5004 | 10 | E | | 001-099 | |
| 0008 | 12 | GA | | 9-0 | 24-51-52 | D40248P | | 8 | | | | TB5004 | 10 | E | | 115-199 | |
| 0009 | 12 | GA | | 9-5 | 24-51-52 | D40248P | | 9 | | | | TB5004 | 11 | E | | 001-099 | |
| 0009 | 12 | GA | | 9-0 | 24-51-52 | D40248P | | 9 | | | | TB5004 | 11 | E | | 115-199 | |
| 0010 | 14 | GA | | 10-4 | 24-53-21 | D40248P | | 10 | | | | TB5002 | 4 | E | | 001-099 | |
| 0010 | 14 | GA | | 12-0 | 24-53-21 | D40248P | | 10 | | | | TB5002 | 4 | E | | 115-199 | |
| 0015 | 22 | GA | | 10-3 | 24-51-72 | TB5002 | | 5 | E | | | D42204P | 5 | | | 001-099 | |
| 0015 | 22 | GA | | 13-0 | 24-51-72 | D42204P | | 5 | | | | TB5002 | 5 | E | | 115-199 | |
| 0016 | 22 | GA | | 10-2 | 24-51-72 | TB5002 | | 6 | E | | | D42204P | 6 | | | 001-099 | |
| 0016 | 22 | GA | | 13-0 | 24-51-72 | D42204P | | 6 | | | | TB5002 | 6 | E | | 115-199 | |
| 0017 | 22 | GA | | 10-1 | 24-51-72 | TB5002 | | 7 | E | | | D42204P | 8 | | | 001-099 | |
| 0017 | 22 | GA | | 13-0 | 24-51-72 | D42204P | | 8 | | | | TB5002 | 7 | E | | 115-199 | |
| W2016 | 286N2016 | | | P6 DISC. TO P11 - BUS PWR CAT. S | | | | | | | | | | | | | |
| 0001 | 12 | GA | | 16-0 | 24-54-73 | D40244P | | 1 | | | | TB5005 | 1 | E | | ALL | |
| 0002 | 16 | GA | | 16-0 | 24-54-73 | D40244P | | 2 | | | | TB5005 | 2 | E | | ALL | |
| 0003 | 08 | HA | | 12-0 | 24-54-71 | TB5011 | | 3 | E | | | TB5006 | 4 | E | | ALL | |
| W2018 | 286N2018 | | | P31 TO P6 - L. BUS FEEDER | | | | | | | | | | | | | |
| 0001 | 06 | HA | | 24-0 | 24-51-11 | C00901 | | L1 | H | | | TB5012 | 1 | F | | ALL | |
| 0002 | 06 | HA | | 24-0 | 24-51-11 | C00901 | | L2 | H | | | TB5012 | 2 | F | | ALL | |
| 0003 | 06 | HA | | 24-0 | 24-51-11 | C00901 | | L3 | H | | | TB5012 | 3 | F | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2010

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2020 | 286N2020 | | | P32 TO P6 - R. BUS FEEDER | | | | | | | | | | | |
| 0001 | 06 | | HA | | 22-6 | 24-51-21 | C00903 | L1 | H | | TB5014 | 1 | F | | 001-099 |
| 0001 | 06 | | HA | | 22-0 | 24-51-21 | C00903 | L1 | H | | TB5014 | 1 | F | | 115-199 |
| 0002 | 06 | | HA | | 22-6 | 24-51-21 | C00903 | L2 | H | | TB5014 | 2 | F | | 001-099 |
| 0002 | 06 | | HA | | 22-0 | 24-51-21 | C00903 | L2 | H | | TB5014 | 2 | F | | 115-199 |
| 0003 | 06 | | HA | | 22-6 | 24-51-21 | C00903 | L3 | H | | TB5014 | 3 | F | | 001-099 |
| 0003 | 06 | | HA | | 22-0 | 24-51-21 | C00903 | L3 | H | | TB5014 | 3 | F | | 115-199 |
| W2021 | 286N2021 | | | WEATHER RADAR ANTENNA TO STA 205 PRESSURE SEAL | | | | | | | | | | | |
| 0001 | 22 | | GA | | 3-0 | 34-43-12 | D00167 | Z- | | | D00473 | 1 | | | ALL |
| 0002 | 22 | | GA | | 3-0 | 34-43-12 | D00167 | I- | | | D00473 | 7 | | | ALL |
| 0003 | 20 | | GA | | 3-0 | 34-43-12 | D00167 | N- | | | D00473 | 6 | | | ALL |
| 0004 | 22 | | GA | | 3-0 | 34-43-12 | D00167 | HH | | | D00473 | 28 | | | ALL |
| 2501B | 22 | | GF | AA | 3-0 | 34-43-12 | D00167 | T- | | | D00473 | 4 | | | ALL |
| 2501R | 22 | | GF | AA | 0-0 | 34-43-12 | D00167 | S- | | | D00473 | 5 | | | ALL |
| 2501Z | | | | AA | 0-0 | 34-43-12 | D00167 | DD | | | D00473 | 3 | | | ALL |
| 2502B | 22 | | GF | AB | 3-0 | 34-43-12 | D00167 | Q- | | | D00473 | 16 | | | ALL |
| 2502R | 22 | | GF | AB | 0-0 | 34-43-12 | D00167 | P- | | | D00473 | 17 | | | ALL |
| 2502Z | | | | AB | 0-0 | 34-43-12 | D00167 | BB | | | D00473 | 15 | | | ALL |
| 2503B | 22 | | GF | AC | 3-0 | 34-43-12 | D00167 | V- | | | D00473 | 9 | | | ALL |
| 2503R | 22 | | GF | AC | 0-0 | 34-43-12 | D00167 | U- | | | D00473 | 10 | | | ALL |
| 2503Z | | | | AC | 0-0 | 34-43-12 | D00167 | EE | | | D00473 | 21 | | | ALL |
| 2504B | 22 | | GF | AD | 3-0 | 34-43-12 | D00167 | Y | | | D00473 | 33 | | | ALL |
| 2504R | 22 | | GF | AD | 0-0 | 34-43-12 | D00167 | X | | | D00473 | 34 | | | ALL |
| 2504Z | | | | AD | 0-0 | 34-43-12 | D00167 | R- | | | D00473 | 32 | | | ALL |
| 2505B | 22 | | GF | AE | 3-0 | 34-43-12 | D00167 | F- | | | D00473 | 30 | | | ALL |
| 2505R | 22 | | GF | AE | 0-0 | 34-43-12 | D00167 | E- | | | D00473 | 31 | | | ALL |
| 2505Z | | | | AE | 0-0 | 34-43-12 | D00167 | W- | | | D00473 | 29 | | | ALL |
| 2506B | 22 | | GF | AF | 3-0 | SPARE | D00167 | CAP | Y | | D00473 | CAP | Y | | ALL |
| 2506R | 22 | | GF | AF | 0-0 | SPARE | D00167 | CAP | Y | | D00473 | CAP | Y | | ALL |
| 2506Z | | | | AF | 0-0 | SPARE | D00167 | DED | | | D00473 | DED | | | ALL |
| 3501B | 22 | | GG | AG | 3-0 | 34-43-12 | D00167 | E | | | D00473 | 8 | | | ALL |
| 3501R | 22 | | GG | AG | 0-0 | 34-43-12 | D00167 | D | | | D00473 | 2 | | | ALL |
| 3501Y | 22 | | GG | AG | 0-0 | 34-43-12 | D00167 | F | | | D00473 | 19 | | | ALL |
| 3501Z | | | | AG | 0-0 | 34-43-12 | D00167 | A- | | | D00473 | 18 | | | ALL |
| 3502B | 22 | | GG | AH | 3-0 | 34-43-12 | D00167 | B | | | D00473 | 13 | | | ALL |
| 3502R | 22 | | GG | AH | 0-0 | 34-43-12 | D00167 | A | | | D00473 | 14 | | | ALL |
| 3502Y | 22 | | GG | AH | 0-0 | 34-43-12 | D00167 | C | | | D00473 | 12 | | | ALL |
| 3502Z | | | | AH | 0-0 | 34-43-12 | D00167 | W | | | D00473 | 11 | | | ALL |
| 3503B | 22 | | GG | AI | 3-0 | 34-43-12 | D00167 | H | | | D00473 | 37 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2020

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-------------|--|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2021 | 286N2021 | | | | | WEATHER RADAR ANTENNA TO STA 205 PRESSURE SEAL (continued) | | | | | | | | | | |
| 3503R | 22 | GG | AI | | 0-0 | 34-43-12 | D00167 | | G | | D00473 | 20 | | | ALL | |
| 3503Y | 22 | GG | AI | | 0-0 | 34-43-12 | D00167 | | J | | D00473 | 36 | | | ALL | |
| 3503Z | | | AI | | 0-0 | 34-43-12 | D00167 | | D- | | D00473 | 35 | | | ALL | |
| YAAA | | | | | 0-0 | 34-43-12 | D00167 | | PER | | D00473 | PER | | | ALL | |
| W2022 | 286N2022 | | | | | P37 TO P6 - GRD. SERVICE BUS FEEDER | | | | | | | | | | |
| 0001 | 08 | HA | | | 26-0 | 24-51-52 | TB5070 | 7 | E | | TB5015 | 1 | E | | 001-099 | |
| 0001 | 08 | HA | | | 27-0 | 24-51-52 | K00102 | A2 | F | | TB5015 | 1 | E | | 115-199 | |
| 0002 | 08 | HA | | | 26-0 | 24-51-52 | TB5070 | 8 | E | | TB5015 | 2 | E | | 001-099 | |
| 0002 | 08 | HA | | | 27-0 | 24-51-52 | K00102 | B2 | F | | TB5015 | 2 | E | | 115-199 | |
| 0003 | 08 | HA | | | 26-0 | 24-51-52 | TB5070 | 9 | E | | TB5015 | 3 | E | | 001-099 | |
| 0003 | 08 | HA | | | 27-0 | 24-51-52 | K00102 | C2 | F | | TB5015 | 3 | E | | 115-199 | |
| W2024 | 286N2024 | | | | | JUMPER BUNDLE CARGO BOTTLE 1 | | | | | | | | | | |
| 0001R | 20 | QZ | | | 1-8 | 26-23-11 | D42144J | 1 | | | D04412 | 1 | | | ALL | |
| 0002R | 20 | QZ | | | 1-8 | 26-23-11 | D42144J | 2 | | | D04412 | 2 | | | ALL | |
| 0003R | 20 | QZ | | | 1-8 | 26-23-11 | D42144J | 3 | | | D04412 | 3 | | | ALL | |
| 0004R | 20 | QZ | | | 2-3 | 26-23-11 | D42144J | 4 | | | D04414 | 1 | | | ALL | |
| 0005R | 20 | QZ | | | 2-3 | 26-23-11 | D42144J | 5 | | | D04414 | 2 | | | ALL | |
| 0006R | 20 | QZ | | | 2-3 | 26-23-11 | D42144J | 6 | | | D04414 | 3 | | | ALL | |
| 0007R | 20 | QZ | | | 0-7 | 26-23-11 | D42144J | 7 | | | D42144J | 8 | | | ALL | |
| W2026 | 286N2026 | | | | | JUMPER BUNDLE CARGO BOTTLE 2 | | | | | | | | | | |
| 0001R | 20 | QZ | | | 2-1 | 26-23-11 | D42146J | 1 | | | D04418 | 1 | | | ALL | |
| 0002R | 20 | QZ | | | 2-1 | 26-23-11 | D42146J | 2 | | | D04418 | 2 | | | ALL | |
| 0003R | 20 | QZ | | | 2-1 | 26-23-11 | D42146J | 3 | | | D04418 | 3 | | | ALL | |
| 0004R | 20 | QZ | | | 1-7 | 26-23-11 | D42146J | 4 | | | D04420 | 1 | | | ALL | |
| 0005R | 20 | QZ | | | 1-7 | 26-23-11 | D42146J | 5 | | | D04420 | 2 | | | ALL | |
| 0006R | 20 | QZ | | | 1-7 | 26-23-11 | D42146J | 6 | | | D04420 | 3 | | | ALL | |
| 0007R | 20 | QZ | | | 0-7 | 26-23-11 | D42146J | 7 | | | D42146J | 8 | | | ALL | |
| W2028 | 286N2028 | | | | | JUMPER BUNDLE, APU FIRE BOTTLE AND DETECTORS | | | | | | | | | | |
| 0001 | 18 | HA | | | 11-4 | 26-18-11 | D41250J | 1 | | | D01970 | = 1 | | | 001-099 | |
| 0003 | 18 | HA | | | 11-3 | 26-18-11 | D41250J | 3 | | | D01974 | = 1 | | | 001-099 | |
| 0005 | 18 | HA | | | 16-2 | 26-18-11 | D41250J | 5 | | | D01978 | = 1 | | | 001-099 | |
| 0006 | 18 | HA | | | 39-10 | 26-18-11 | D41250J | 6 | | | D01980 | = 1 | | | 001-099 | |
| 0007 | 18 | HA | | | 16-2 | 26-18-11 | D41250J | 7 | | | D01982 | = 1 | | | 001-099 | |
| 0008 | 18 | HA | | | 39-10 | 26-18-11 | D41250J | 8 | | | D01984 | = 1 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2020

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2028 | 286N2028 | | | JUMPER BUNDLE, APU FIRE BOTTLE AND DETECTORS (continued) | | | | | | | | | | | |
| 0009 | 18 | GA | | 45-11 | 26-22-21 | D41250J | | 9 | | | D02262 | 1 | 18 | | 001-099 |
| 0010 | 18 | GA | | 48-3 | 26-22-21 | D41250J | | 10 | | | D02264 | 1 | 18 | | 001-002 |
| 0010 | 18 | GA | | 43-5 | 26-22-21 | D41250J | | 10 | | | D02264 | 1 | 18 | | 003-099 |
| 0011R | 22 | QA | | 40-7 | 26-15-11 | D41250J | | 11 | | | D40316J | 6 | | | 001-099 |
| 0012R | 22 | QA | | 40-7 | 26-15-11 | D41250J | | 12 | | | D40316J | 4 | | | 001-099 |
| 0013 | 18 | GA | | 10-4 | 26-22-21 | D02262 | | 2 | 18 | | GD01607 | DC.. | GW | | 001-099 |
| 0014 | 18 | GA | | 10-1 | 26-22-21 | D02262 | | 3 | 18 | | GD01608 | ST.. | GW | | 001-099 |
| 0015 | 18 | GA | | 11-0 | 26-22-21 | D02264 | | 3 | 18 | | GD01607 | DC.. | GW | | 001-002 |
| 0015 | 18 | GA | | 7-10 | 26-22-21 | D02264 | | 3 | 18 | | GD01607 | DC.. | GW | | 003-099 |
| 0016 | 18 | GA | | 11-0 | 26-22-21 | D02264 | | 4 | 18 | | GD01608 | ST.. | GW | | 001-002 |
| 0016 | 18 | GA | | 7-7 | 26-22-21 | D02264 | | 4 | 18 | | GD01608 | ST.. | GW | | 003-099 |
| 0017R | 20 | QA | | 40-7 | SPARE | D41250J | | 13 | | | D40316J | 2 | | | 001-002 |
| 0017R | 20 | QA | | 4-2 | 26-15-11 | GD00339 | DC.. | GW | | | D40316J | 2 | | | 003-099 |
| 0018R | 20 | QA | | 40-7 | SPARE | D41250J | | 14 | | | D40316J | 1 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2020

Page 3 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2034 | 286N2034 | | | FWD EQUIP AREA TO P6 MAIN BATT CHARGER CONTROL | | | | | | | | | | | |
| 0001 | 20 | | GA | | 25-0 | 24-31-11 | D40282P | | 1 | | D02082 | | 4 | | 001-099 |
| 0001 | 20 | | GA | | 26-0 | 24-31-11 | D40282P | | 1 | | D02082 | | 4 | | 115-199 |
| 0002 | 20 | | GA | | 25-0 | 24-31-11 | D40282P | | 2 | | D02082 | | 7 | | 001-099 |
| 0002 | 20 | | GA | | 26-0 | 24-31-11 | D40282P | | 2 | | D02082 | | 7 | | 115-199 |
| 0003 | 20 | | GA | | 25-0 | 24-31-11 | D40282P | | 3 | | D02082 | | 10 | | 001-099 |
| 0003 | 20 | | GA | | 26-0 | 24-31-11 | D40282P | | 3 | | D02082 | | 10 | | 115-199 |
| 0004 | 20 | | GA | | 25-0 | 24-31-11 | D40282P | | 4 | | D02082 | | 8 | | 001-099 |
| 0004 | 20 | | GA | | 26-0 | 24-31-11 | D40282P | | 4 | | D02082 | | 8 | | 115-199 |
| 0005 | 22 | | GA | | 25-0 | 24-34-11 | D40282P | | 5 | | D02082 | | 9 | | 001-099 |
| 0005 | 22 | | GA | | 26-0 | 24-34-11 | D40282P | | 5 | | D02082 | | 9 | | 115-199 |
| 0006 | 24 | | GK | | 16-0 | 24-31-11 | D40282P | | 6 | | D01794 | | 8 | | ALL |
| 0007 | 20 | | GA | | 7-0 | 24-31-11 | D02082 | | 2 | | GD00533 | ST.. | E | | 001-099 |
| 0007 | 20 | | GA | | 4-0 | 24-31-11 | D02082 | | 2 | | GD00533 | ST.. | E | | 115-199 |
| 0008 | 24 | | GK | | 22-0 | 24-31-11 | D02082 | | 1 | | D01794 | | 1 | | 001-099 |
| 0008 | 24 | | GK | | 21-0 | 24-31-11 | D02082 | | 1 | | D01794 | | 1 | | 115-199 |
| 0009 | 24 | | GK | | 22-0 | 24-31-11 | D02082 | | 3 | | D01794 | | 3 | | 001-099 |
| 0009 | 24 | | GK | | 21-0 | 24-31-11 | D02082 | | 3 | | D01794 | | 3 | | 115-199 |
| 0010 | 24 | | GK | | 22-0 | 24-31-11 | D02082 | | 11 | | D01794 | | 12 | | 001-009 |
| 0010 | 24 | | GK | | 21-0 | 24-31-11 | D02082 | | 11 | | D01794 | | 12 | | 115-199 |
| 0011 | 24 | | GK | | 22-0 | 24-31-11 | D02082 | | 12 | | D01794 | | 11 | | 001-009 |
| 0011 | 24 | | GK | | 21-0 | 24-31-11 | D02082 | | 12 | | D01794 | | 11 | | 115-199 |
| 0012 | 22 | | GA | | 1-0 | 24-31-11 | D02082 | | 5 | | D02082 | | 6 | | ALL |
| 0013 | 20 | | GA | | 5-0 | 24-31-11 | D01794 | | 9 | | GD00534 | DC.. | E | | 001-099 |
| 0013 | 20 | | GA | | 3-0 | 24-31-11 | D01794 | | 9 | | GD00534 | DC.. | E | | 115-199 |
| 0014 | 22 | | GA | | 16-0 | 24-34-11 | D01854 | | 4 | | D40282P | | 7 | | ALL |
| 0015 | 22 | | GA | | 16-0 | 24-31-11 | D01854 | | 7 | | D40282P | | 8 | | ALL |
| 0016 | 22 | | GA | | 16-0 | 24-34-11 | D01854 | | 11 | | D40282P | | 9 | | ALL |
| 0017 | 22 | | GA | | 5-0 | 24-34-11 | D01854 | | 9 | | GD00535 | DC.. | E | | 001-099 |
| 0017 | 22 | | GA | | 3-0 | 24-34-11 | D01854 | | 9 | | GD00535 | DC.. | E | | 115-199 |
| 0018 | 20 | | GA | | 4-0 | 24-31-11 | D01854 | | 2 | | GD03518 | ST.. | E | | 001-099 |
| 0018 | 20 | | GA | | 3-0 | 24-31-11 | D01854 | | 2 | | GD03518 | ST.. | E | | 115-199 |
| 0019 | 22 | | GA | | 5-0 | 24-31-11 | D02082 | | | FB | GD00533 | ST.. | E | | 010-099 |
| 0020 | 22 | | GA | | 4-0 | 24-31-11 | D01794 | | | FA | GD03518 | ST.. | E | | 010-099 |
| 2001B | 22 | | GB | AA | 15-0 | 24-34-11 | M00224 | | D | D | D40282P | | 11 | | 001-099 |
| 2001B | 22 | | GB | AA | 16-0 | 24-34-11 | M00224 | | D | D | D40282P | | 11 | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 24-34-11 | M00224 | | C | D | D40282P | | 10 | | ALL |
| 2501B | 24 | | G2 | AC | 22-0 | 24-31-11 | D01794 | | 11 | | D02082 | | 12 | | 010-099 |
| 2501R | 24 | | G2 | AC | 0-0 | 24-31-11 | D01794 | | 12 | | D02082 | | 11 | | 010-099 |
| 2501Z | | | | AC | 0-0 | 24-31-11 | D01794 | | | FA | D02082 | | | FB | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W2030

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-------------|------------------------------------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2036 | 286N2036 | | | | | P30 TO P34 - EXT PWR RECPT FEEDERS | | | | | | | | | | |
| 0001 | *1 | | CQ | | 7-0 | 24-41-11 | D01718 | | A | H | | K00114 | A1 | H | | ALL |
| 0002 | *1 | | CQ | | 6-0 | 24-41-11 | D01718 | | B | H | | K00114 | B1 | H | | 001-099 |
| 0002 | *1 | | CQ | | 7-0 | 24-41-11 | D01718 | | B | H | | K00114 | B1 | H | | 115-199 |
| 0003 | *1 | | CQ | | 6-0 | 24-41-11 | D01718 | | C | H | | K00114 | C1 | H | | ALL |
| 0004 | *1 | | ZC | | 1-1 | 24-41-11 | D01718 | | N | R | | GD00536 | AC.. | R | | ALL |
| W2038 | 286N2038 | | | | | P30 TO P34 - EXT. POWER CONTROL | | | | | | | | | | |
| 0001 | 24 | | GK | | 7-0 | 24-41-11 | D01718 | | E | E | | D40378P | 1 | | | 001-099 |
| 0001 | 20 | | GA | | 7-0 | 24-41-11 | D01718 | | E | E | | D40378P | 1 | | | 115-199 |
| 0002 | 24 | | GK | | 7-0 | 24-41-11 | D01718 | | F | E | | D40378P | 2 | | | 001-099 |
| 0002 | 20 | | GA | | 7-0 | 24-41-11 | D01718 | | F | E | | D40378P | 2 | | | 115-199 |
| 0003 | 20 | | GA | | 4-0 | 24-41-12 | L00004 | | 2 | I | | GD00538 | DC.. | E | | 001-099 |
| 0003 | 20 | | GA | | 5-0 | 24-41-12 | L00004 | | 2 | I | | GD00538 | DC.. | E | | 115-199 |
| 0004 | 24 | | GK | | 7-0 | 24-41-12 | D40378P | | 3 | | | L00004 | 1 | C | | ALL |
| 0005 | 24 | | GK | | 7-0 | 24-41-12 | D40378P | | 4 | | | L00005 | 2 | C | | ALL |
| 0006 | 24 | | GK | | 3-0 | 24-41-12 | L00004 | | 1 | C | | L00005 | 1 | C | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2030

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W2041 | 286N2041 | | | P55 GLARE SHIELD-M90,M91 PANELS TO AP0001 | | | | | | | | | | | |
| 0003 | 22 | GA | | | 11-0 | 22-11-12 | D00037 | 7 | | | D40629P | 1 | | | 001-099 |
| 0003 | 22 | GA | | | 9-0 | 22-11-12 | D00037 | 7 | | | D40629P | 1 | | | 115-199 |
| 0004 | 22 | GA | | | 9-0 | 22-11-12 | D00037 | 22 | | | D40629P | 2 | | | 115-199 |
| 0005 | 22 | GA | | | 10-0 | 22-11-12 | D00037 | 30 | | | D40629P | 3 | | | 001-099 |
| 0005 | 22 | GA | | | 9-0 | 22-11-12 | D00037 | 30 | | | D40629P | 3 | | | 115-199 |
| 0006 | 22 | GA | | | 10-0 | 22-11-12 | D00037 | 5 | | | D40629P | 4 | | | 001-099 |
| 0006 | 22 | GA | | | 9-0 | 22-11-12 | D00037 | 5 | | | D40629P | 4 | | | 115-199 |
| 0008 | 20 | GA | | | 11-0 | 22-11-12 | D00037 | 18 | | | GD01009 | DC.. | 2 | | 001-099 |
| 0008 | 20 | GA | | | 10-0 | 22-11-12 | D00037 | 18 | | | GD01009 | DC.. | 2 | | 115-199 |
| 0009 | 20 | GA | | | 11-0 | 22-11-12 | D00037 | 19 | | | GD01009 | ST.. | 2 | | 001-099 |
| 0009 | 20 | GA | | | 10-0 | 22-11-12 | D00037 | 19 | | | GD01009 | ST.. | 2 | | 115-199 |
| 0010 | 20 | PA | | | 10-0 | 22-11-12 | D00037 | 10 | | | GD01009 | DC.. | 2 | | 115-199 |
| 0013 | 22 | GA | | | 9-0 | 34-55-11 | D00259 | 7 | | | D40629P | 14 | | | ALL |
| 0014 | 22 | GA | | | 9-0 | 34-51-11 | D00259 | 6 | | | D40629P | 23 | | | ALL |
| 0015 | 22 | GA | | | 12-0 | 33-16-11 | D00037 | 9 | | | TB0013Y | C007 | BJ | | 001-099 |
| 0015 | 22 | GA | | | 11-0 | 33-16-11 | D00037 | 9 | | | TB0013Y | C007 | BJ | | 115-199 |
| 0016 | 22 | GA | | | 12-0 | 33-16-21 | D00037 | 3 | | | TB0013Y | C008 | BJ | | 001-099 |
| 0016 | 22 | GA | | | 11-0 | 33-16-21 | D00037 | 3 | | | TB0013Y | C008 | BJ | | 115-199 |
| 0017 | 24 | GK | | | 11-0 | 22-32-15 | D00037 | 8 | | | D40629P | 47 | | | 001-099 |
| 0017 | 24 | GK | | | 9-0 | 22-32-15 | D00037 | 8 | | | D40629P | 47 | | | 115-199 |
| 0018 | 24 | GK | | | 11-0 | 22-32-15 | D00037 | 25 | | | D40629P | 48 | | | 001-099 |
| 0018 | 24 | GK | | | 9-0 | 22-32-15 | D00037 | 25 | | | D40629P | 48 | | | 115-199 |
| 0019 | 20 | GA | | | 10-0 | 34-55-11 | D00263 | 6 | | | GD01009 | DC.. | 2 | | ALL |
| 0020 | 20 | GA | | | 10-0 | 34-55-11 | D00263 | 12 | | | GD01009 | ST.. | 2 | | ALL |
| 0021 | 20 | GA | | | 10-0 | 33-13-41 | D00263 | 2 | | | GD01009 | AC.. | 2 | | ALL |
| 0022 | 20 | GA | | | 5-0 | 33-13-41 | D00263 | 1 | | | SP00211 | | W | | ALL |
| 0023 | 22 | GA | | | 12-0 | 33-16-51 | D00263 | 5 | | | TB0015Z | 13 | BJ | | ALL |
| 0024 | 22 | GA | | | 11-0 | 33-16-61 | D00263 | 4 | | | TB0013X | C015 | BJ | | ALL |
| 0025 | 24 | GK | | | 11-0 | 34-22-18 | D00259 | 26 | | | TB0013Y | A011 | BJ | | ALL |
| 0026 | 24 | GK | | | 10-0 | 34-22-18 | D00259 | 27 | | | TB0013Z | 27 | BJ | | ALL |
| 0027 | 22 | GA | | | 9-0 | SPARE | D00037 | | CAP | Y | D40629P | 27 | | | 115-199 |
| 0028 | 20 | GA | | | 10-0 | 22-11-12 | D00037 | 11 | | | GD01009 | DC.. | 2 | | 115-199 |
| 0029 | 22 | GA | | | 9-0 | SPARE | D00259 | | CAP | Y | D40629P | 35 | | | 115-199 |
| 0030 | 22 | GA | | | 9-0 | SPARE | D00259 | | CAP | Y | D40629P | 36 | | | 115-199 |
| 0031 | 20 | GA | | | 10-0 | 34-51-11 | D00259 | 14 | | | GD01014 | DC.. | 2 | | ALL |
| 0033 | 22 | GA | | | 9-0 | 34-12-12 | D00037 | 13 | | | D40629P | 53 | | | 115-199 |
| 0034 | 22 | GA | | | 9-0 | 34-12-12 | D00037 | 14 | | | D40629P | 52 | | | 115-199 |
| 2001B | 22 | GB | AF | | 9-0 | 34-51-11 | D00259 | 2 | | | D40629P | 22 | | | ALL |
| 2001R | 22 | GB | AF | | 0-0 | 34-51-11 | D00259 | 1 | | | D40629P | 21 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2040

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2041 | 286N2041 | | | | P55 GLARE SHIELD-M90,M91 PANELS TO AP0001 (continued) | | | | | | | | | | |
| 3501B | 24 | G3 | AH | | 9-0 | 23-51-12 | D00259 | 25 | | | D40629P | 41 | | | ALL |
| 3501R | 24 | G3 | AH | | 0-0 | 23-51-12 | D00259 | 24 | | | D40629P | 40 | | | ALL |
| 3501Y | 24 | G3 | AH | | 0-0 | 23-51-12 | D00259 | 12 | | | D40629P | 42 | | | ALL |
| 3501Z | | | AH | | 0-0 | 23-51-12 | D00259 | DED | | | D40629P | 43 | | | ALL |
| 5001B | 24 | G2 | AA | | 10-0 | 22-12-11 | D00037 | 21 | | | D40629P | 6 | | | 001-099 |
| 5001B | 24 | G2 | AA | | 9-0 | 22-12-11 | D00037 | 21 | | | D40629P | 6 | | | 115-199 |
| 5001R | 24 | G2 | AA | | 0-0 | 22-12-11 | D00037 | 20 | | | D40629P | 5 | | | ALL |
| 5001Z | | | AA | | 0-0 | 22-12-11 | GD01000 | ST.. | E | *1 | D40629P | 7 | | | ALL |
| 5002B | 24 | G2 | AB | | 10-0 | 22-13-11 | D00037 | 29 | | | D40629P | 9 | | | 001-099 |
| 5002B | 24 | G2 | AB | | 9-0 | 22-13-11 | D00037 | 29 | | | D40629P | 9 | | | 115-199 |
| 5002R | 24 | G2 | AB | | 0-0 | 22-13-11 | D00037 | 28 | | | D40629P | 8 | | | ALL |
| 5002Z | | | AB | | 0-0 | 22-13-11 | GD01000 | ST.. | E | *1 | D40629P | 10 | | | ALL |
| 5003B | 24 | G2 | AC | | 9-0 | 34-55-11 | D00259 | 29 | | | D40629P | 12 | | | ALL |
| 5003R | 24 | G2 | AC | | 0-0 | 34-55-11 | D00259 | 16 | | | D40629P | 11 | | | ALL |
| 5003Z | | | AC | | 0-0 | 34-55-11 | D00259 | 28 | | | D40629P | 13 | | | ALL |
| 5004B | 24 | G2 | AD | | 10-0 | 34-51-11 | D00259 | 21 | | | D40629P | 16 | | | 001-099 |
| 5004B | 24 | G2 | AD | | 9-0 | 34-51-11 | D00259 | 21 | | | D40629P | 16 | | | 115-199 |
| 5004R | 24 | G2 | AD | | 0-0 | 34-51-11 | D00259 | 8 | | | D40629P | 15 | | | ALL |
| 5004Z | | | AD | | 0-0 | 34-51-11 | D00259 | 20 | | | D40629P | 17 | | | ALL |
| 5005B | 24 | G2 | AE | | 9-0 | 34-51-11 | D00259 | 31 | | | D40629P | 19 | | | ALL |
| 5005R | 24 | G2 | AE | | 0-0 | 34-51-11 | D00259 | 18 | | | D40629P | 18 | | | ALL |
| 5005Z | | | AE | | 0-0 | 34-51-11 | D00259 | 30 | | | D40629P | 20 | | | ALL |
| 5006B | 24 | G2 | AG | | 9-0 | 34-31-11 | D00259 | 22 | | | D40629P | 25 | | | ALL |
| 5006R | 24 | G2 | AG | | 0-0 | 34-31-11 | D00259 | 10 | | | D40629P | 24 | | | ALL |
| 5006Z | | | AG | | 0-0 | 34-31-11 | D00259 | 23 | | | D40629P | 26 | | | ALL |
| 5007B | 24 | G2 | AJ | | 10-0 | 22-14-11 | D00037 | 23 | | | D40629P | 50 | | | 001-099 |
| 5007B | 24 | G2 | AJ | | 9-0 | 22-14-11 | D00037 | 23 | | | D40629P | 50 | | | 115-199 |
| 5007R | 24 | G2 | AJ | | 0-0 | 22-14-11 | D00037 | 24 | | | D40629P | 49 | | | ALL |
| 5007Z | | | AJ | | 0-0 | 22-14-11 | GD01000 | ST.. | E | *2 | D40629P | 51 | | | ALL |
| 5008B | 24 | G2 | AK | | 11-0 | 22-14-11 | D00037 | 27 | | | TB0013Y | C026 | BJ | | 001-099 |
| 5008B | 24 | G2 | AK | | 10-0 | 22-14-11 | D00037 | 27 | | | TB0013Y | C026 | BJ | | 115-199 |
| 5008R | 24 | G2 | AK | | 0-0 | 22-14-11 | D00037 | 26 | | | TB0013Y | A026 | BJ | | ALL |
| 5008Z | | | AK | | 0-0 | 22-14-11 | GD01000 | ST.. | E | *2 | GD01020 | ST.. | 2 | | ALL |
| W2042 | 286N2042 | | | | P33 TO CAPTAIN & L AUX PITOT PROBE | | | | | | | | | | |
| 0001 | 20 | GA | | | 46-0 | 30-31-11 | D42030P | 1 | | | D02756 | = A | | | 001-099 |
| 0001 | 20 | GA | | | 45-0 | 30-31-11 | D42030P | 1 | | | D02756 | = A | | | 115-199 |
| 0002 | 20 | GA | | | 46-0 | 30-31-11 | D42030P | 2 | | | D02756 | = B | | | 001-099 |
| 0002 | 20 | GA | | | 45-0 | 30-31-11 | D42030P | 2 | | | D02756 | = B | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2040

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2042 | 286N2042 | | | P33 TO CAPTAIN & L AUX PITOT PROBE (continued) | | | | | | | | | | | |
| 0003 | 20 | GA | | | 46-0 | 30-31-11 | D42030P | 3 | | | D02758 | = A | | | 001-099 |
| 0004 | 20 | GA | | | 46-0 | 30-31-11 | D42030P | 4 | | | D02758 | = B | | | 001-099 |
| W2045 | 286N2045 | | | LEFT STICK SHAKER | | | | | | | | | | | |
| 0001 | 22 | 6A | | | 6-0 | 27-32-11 | D00519 | A | | | SP00173 | | 9 | | ALL |
| 0002 | 22 | 6A | | | 6-0 | 27-32-11 | D00519 | B | | | SP00175 | | 9 | | ALL |
| W2048 | 286N2048 | | | JUMPER BUNDLE, APU FIRE DETECTOR | | | | | | | | | | | |
| 0001R | 22 | QA | | | 31-11 | 26-15-11 | D41254J | 1 | | | D40318J | | 4 | | 001-099 |
| 0002R | 22 | QA | | | 31-11 | 26-15-11 | D41254J | 2 | | | D40318J | | 6 | | 001-099 |
| 0003R | 20 | QA | | | 31-11 | SPARE | D41254J | 3 | | | D40318J | | 2 | | 001-002 |
| 0003R | 20 | QA | | | 3-11 | 26-15-11 | GD00339 | DC.. | GW | | D40318J | | 2 | | 003-099 |
| 0004R | 20 | QA | | | 31-11 | SPARE | D41254J | 4 | | | D40318J | | 5 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2040

Page 3 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2051 | 286N2051 | | | P55 GLARE SHIELD M90,M92 PANELS TO AP0003 | | | | | | | | | | | |
| 0003 | 24 | | GK | | 9-2 | 34-22-28 | D00261 | | 27 | | TB0016Z | 11 | BJ | | 001-099 |
| 0003 | 24 | | GK | | 9-0 | 34-22-28 | D00261 | | 27 | | TB0016Z | 11 | BJ | | 115-199 |
| 0004 | 24 | | GK | | 9-2 | 34-22-28 | D00261 | | 26 | | TB0016Y | A007 | BJ | | 001-099 |
| 0004 | 24 | | GK | | 9-0 | 34-22-28 | D00261 | | 26 | | TB0016Y | A007 | BJ | | 115-199 |
| 0005 | 22 | | GA | | 8-5 | 22-11-22 | D00077 | | 5 | | D40631P | 10 | | | 001-099 |
| 0005 | 22 | | GA | | 9-0 | 22-11-22 | D00077 | | 5 | | D40631P | 10 | | | 115-199 |
| 0006 | 22 | | GA | | 8-5 | 22-11-22 | D00077 | | 7 | | D40631P | 11 | | | 001-099 |
| 0006 | 22 | | GA | | 9-0 | 22-11-22 | D00077 | | 7 | | D40631P | 11 | | | 115-199 |
| 0007 | 22 | | GA | | 9-0 | 22-11-22 | D00077 | | 22 | | D40631P | 12 | | | 115-199 |
| 0008 | 22 | | GA | | 8-5 | 22-11-22 | D00077 | | 30 | | D40631P | 13 | | | 001-099 |
| 0008 | 22 | | GA | | 9-0 | 22-11-22 | D00077 | | 30 | | D40631P | 13 | | | 115-199 |
| 0009 | 20 | | GA | | 9-0 | 22-11-22 | D00077 | | 11 | | GD01241 | DC.. | 2 | | 115-199 |
| 0010 | 20 | | GA | | 9-6 | 22-11-22 | D00077 | | 18 | | GD01241 | DC.. | 2 | | 001-099 |
| 0010 | 20 | | GA | | 10-0 | 22-11-22 | D00077 | | 18 | | GD01241 | DC.. | 2 | | 115-199 |
| 0011 | 20 | | GA | | 9-6 | 22-11-22 | D00077 | | 19 | | GD01241 | ST.. | 2 | | 001-099 |
| 0011 | 20 | | GA | | 10-0 | 22-11-22 | D00077 | | 19 | | GD01241 | ST.. | 2 | | 115-199 |
| 0012 | 20 | | GA | | 9-6 | 34-51-21 | D00261 | | 14 | | GD01241 | DC.. | 2 | | 001-099 |
| 0012 | 20 | | GA | | 10-0 | 34-51-21 | D00261 | | 14 | | GD01241 | DC.. | 2 | | 115-199 |
| 0013 | 22 | | GA | | 8-5 | 34-51-21 | D00261 | | 6 | | D40631P | 28 | | | 001-099 |
| 0013 | 22 | | GA | | 9-0 | 34-51-21 | D00261 | | 6 | | D40631P | 28 | | | 115-199 |
| 0014 | 24 | | GK | | 8-5 | 34-55-21 | D00261 | | 7 | | D40631P | 16 | | | 001-099 |
| 0014 | 24 | | GK | | 9-0 | 34-55-21 | D00261 | | 7 | | D40631P | 16 | | | 115-199 |
| 0015 | 20 | | GA | | 9-6 | 34-55-21 | D00265 | | 6 | | GD01241 | DC.. | 2 | | 001-099 |
| 0015 | 20 | | GA | | 10-0 | 34-55-21 | D00265 | | 6 | | GD01241 | DC.. | 2 | | 115-199 |
| 0016 | 20 | | GA | | 9-6 | 34-55-21 | D00265 | | 12 | | GD01241 | ST.. | 2 | | 001-099 |
| 0016 | 20 | | GA | | 10-0 | 34-55-21 | D00265 | | 12 | | GD01241 | ST.. | 2 | | 115-199 |
| 0017 | 22 | | GA | | 9-2 | 33-16-41 | D00265 | | 4 | | TB0015Y | A012 | BJ | | 001-099 |
| 0017 | 22 | | GA | | 9-0 | 33-16-41 | D00265 | | 4 | | TB0015Y | A012 | BJ | | 115-199 |
| 0018 | 22 | | GA | | 9-2 | 33-16-41 | D00265 | | 5 | | TB0015Z | 14 | BJ | | 001-099 |
| 0018 | 22 | | GA | | 9-0 | 33-16-41 | D00265 | | 5 | | TB0015Z | 14 | BJ | | 115-199 |
| 0019 | 22 | | GA | | 9-2 | 33-16-41 | D00077 | | 3 | | TB0015Y | C012 | BJ | | 001-099 |
| 0019 | 22 | | GA | | 9-0 | 33-16-41 | D00077 | | 3 | | TB0015Y | C012 | BJ | | 115-199 |
| 0020 | 22 | | GA | | 9-2 | 33-16-41 | D00077 | | 9 | | TB0015Z | 14 | BJ | | 001-099 |
| 0020 | 22 | | GA | | 9-0 | 33-16-41 | D00077 | | 9 | | TB0015Z | 14 | BJ | | 115-199 |
| 0021 | 20 | | GA | | 4-1 | 33-13-41 | D00265 | | 1 | | SP00209 | | 9 | | 001-099 |
| 0021 | 20 | | GA | | 7-0 | 33-13-41 | D00265 | | 1 | | SP00209 | | 9 | | 115-199 |
| 0022 | 20 | | GA | | 9-6 | 33-13-41 | D00265 | | 2 | | GD01241 | AC.. | 2 | | 001-099 |
| 0022 | 20 | | GA | | 10-0 | 33-13-41 | D00265 | | 2 | | GD01241 | AC.. | 2 | | 115-199 |
| 0023 | 22 | | GA | | 9-0 | SPARE | D00077 | | CAP | Y | D40631P | 14 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2050

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2051 | 286N2051 | | | P55 GLARE SHIELD M90,M92 PANELS TO AP0003 (continued) | | | | | | | | | | | |
| 0024 | 22 | GA | | | 9-0 | SPARE | D00077 | CAP | Y | | D40631P | 15 | | | 115-199 |
| 0025 | 20 | PA | | | 9-0 | 22-11-22 | D00077 | 10 | | | GD01241 | DC.. | 2 | | 115-199 |
| 0026 | 22 | GA | | | 9-0 | SPARE | D00261 | CAP | Y | | D40631P | 37 | | | 115-199 |
| 0027 | 22 | GA | | | 9-0 | 34-12-22 | D00077 | 13 | | | D40631P | 45 | | | 115-199 |
| 0028 | 22 | GA | | | 9-0 | 34-12-22 | D00077 | 14 | | | D40631P | 44 | | | 115-199 |
| 2001B | 22 | GB | AH | | 8-5 | 34-51-21 | D00261 | 2 | | | D40631P | 27 | | | 001-099 |
| 2001B | 22 | GB | AH | | 9-0 | 34-51-21 | D00261 | 2 | | | D40631P | 27 | | | 115-199 |
| 2001R | 22 | GB | AH | | 0-0 | 34-51-21 | D00261 | 1 | | | D40631P | 26 | | | ALL |
| 3501B | 24 | G3 | AK | | 8-5 | 23-51-12 | D00261 | 25 | | | D40631P | 33 | | | 001-099 |
| 3501B | 24 | G3 | AK | | 9-0 | 23-51-12 | D00261 | 25 | | | D40631P | 33 | | | 115-199 |
| 3501R | 24 | G3 | AK | | 0-0 | 23-51-12 | D00261 | 24 | | | D40631P | 32 | | | ALL |
| 3501Y | 24 | G3 | AK | | 0-0 | 23-51-12 | D00261 | 12 | | | D40631P | 34 | | | ALL |
| 3501Z | | | AK | | 0-0 | 23-51-12 | D00261 | DED | | | D40631P | 35 | | | ALL |
| 5001B | 24 | G2 | AA | | 8-5 | 22-12-21 | D00077 | 21 | | | D40631P | 2 | | | 001-099 |
| 5001B | 24 | G2 | AA | | 9-0 | 22-12-21 | D00077 | 21 | | | D40631P | 2 | | | 115-199 |
| 5001R | 24 | G2 | AA | | 0-0 | 22-12-21 | D00077 | 20 | | | D40631P | 1 | | | ALL |
| 5001Z | | | AA | | 0-0 | 22-12-21 | GD01001 | ST.. | E | * | D40631P | 3 | | | ALL |
| 5002B | 24 | G2 | AB | | 8-5 | 22-13-21 | D00077 | 29 | | | D40631P | 5 | | | 001-099 |
| 5002B | 24 | G2 | AB | | 9-0 | 22-13-21 | D00077 | 29 | | | D40631P | 5 | | | 115-199 |
| 5002R | 24 | G2 | AB | | 0-0 | 22-13-21 | D00077 | 28 | | | D40631P | 4 | | | ALL |
| 5002Z | | | AB | | 0-0 | 22-13-21 | GD01001 | ST.. | E | * | D40631P | 6 | | | ALL |
| 5003B | 24 | G2 | AC | | 8-5 | 22-14-21 | D00077 | 23 | | | D40631P | 8 | | | 001-099 |
| 5003B | 24 | G2 | AC | | 9-0 | 22-14-21 | D00077 | 23 | | | D40631P | 8 | | | 115-199 |
| 5003R | 24 | G2 | AC | | 0-0 | 22-14-21 | D00077 | 24 | | | D40631P | 7 | | | ALL |
| 5003Z | | | AC | | 0-0 | 22-14-21 | D40631P | 9 | | | GD01001 | ST.. | E | *1 | ALL |
| 5004B | 24 | G2 | AD | | 9-2 | 22-14-21 | D00077 | 27 | | | TB0016Y | A015 | BJ | | 001-099 |
| 5004B | 24 | G2 | AD | | 9-0 | 22-14-21 | D00077 | 27 | | | TB0016Y | A015 | BJ | | 115-199 |
| 5004R | 24 | G2 | AD | | 0-0 | 22-14-21 | D00077 | 26 | | | TB0016Y | C015 | BJ | | ALL |
| 5004Z | | | AD | | 0-0 | 22-14-21 | GD01001 | ST.. | E | *1 | GD01241 | ST.. | 2 | | ALL |
| 5005B | 24 | G2 | AE | | 8-5 | 34-51-21 | D00261 | 22 | | | D40631P | 21 | | | 001-099 |
| 5005B | 24 | G2 | AE | | 9-0 | 34-51-21 | D00261 | 22 | | | D40631P | 21 | | | 115-199 |
| 5005R | 24 | G2 | AE | | 0-0 | 34-51-21 | D00261 | 10 | | | D40631P | 20 | | | ALL |
| 5005Z | | | AE | | 0-0 | 34-51-21 | D00261 | 23 | | | D40631P | 22 | | | ALL |
| 5006B | 24 | G2 | AF | | 8-5 | 34-51-21 | D00261 | 21 | | | D40631P | 24 | | | 001-099 |
| 5006B | 24 | G2 | AF | | 9-0 | 34-51-21 | D00261 | 21 | | | D40631P | 24 | | | 115-199 |
| 5006R | 24 | G2 | AF | | 0-0 | 34-51-21 | D00261 | 8 | | | D40631P | 23 | | | ALL |
| 5006Z | | | AF | | 0-0 | 34-51-21 | D00261 | 20 | | | D40631P | 25 | | | ALL |
| 5007B | 24 | G2 | AG | | 8-5 | 34-51-21 | D00261 | 31 | | | D40631P | 30 | | | 001-099 |
| 5007B | 24 | G2 | AG | | 9-0 | 34-51-21 | D00261 | 31 | | | D40631P | 30 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2050

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2051 | 286N2051 | | | | P55 GLARE SHIELD M90,M92 PANELS TO AP0003 (continued) | | | | | | | | | | |
| 5007R | 24 | G2 | | AG | 0-0 | 34-51-21 | D00261 | | 18 | | D40631P | 29 | | | ALL |
| 5007Z | | | | AG | 0-0 | 34-51-21 | D00261 | | 30 | | D40631P | 31 | | | ALL |
| 5008B | 24 | G2 | | AJ | 8-5 | 34-55-21 | D00261 | | 29 | | D40631P | 18 | | | 001-099 |
| 5008B | 24 | G2 | | AJ | 9-0 | 34-55-21 | D00261 | | 29 | | D40631P | 18 | | | 115-199 |
| 5008R | 24 | G2 | | AJ | 0-0 | 34-55-21 | D00261 | | 16 | | D40631P | 17 | | | ALL |
| 5008Z | | | | AJ | 0-0 | 34-55-21 | D00261 | | 28 | | D40631P | 19 | | | ALL |
| W2052 | 286N2052 | | | | P37,E/E BAY TO NOSE GEAR WHEELWELL DISC. | | | | | | | | | | |
| 0001 | 18 | GA | | | 23-0 | 33-42-21 | D40488J | | A | | D40490P | 1 | | | 001-099 |
| 0001 | 18 | GA | | | 14-0 | 33-42-21 | D40488J | | A | | D40490P | 1 | | | 115-199 |
| 0002 | 16 | GA | | | 7-0 | 33-42-21 | D40488J | | B | | GD00028 | ST.. | E | | 001-099 |
| 0002 | 16 | GA | | | 9-0 | 33-42-21 | D40488J | | B | | GD00028 | ST.. | E | | 115-199 |
| 0003 | 20 | GA | | | 23-0 | 33-51-11 | D40488J | | C | | D40490P | 2 | | | 001-099 |
| 0003 | 18 | GA | | | 14-0 | 33-51-11 | D40488J | | C | | D40490P | 2 | | | 115-199 |
| 0004 | 20 | GA | | | 23-0 | 33-51-11 | D40488J | | D | | D40490P | 3 | | | 001-099 |
| 0004 | 18 | GA | | | 14-0 | 33-51-11 | D40488J | | D | | D40490P | 3 | | | 115-199 |
| 0005 | 20 | GA | | | 23-0 | 33-51-11 | D40488J | | E | | D40490P | 4 | | | 001-099 |
| 0005 | 18 | GA | | | 14-0 | 33-51-11 | D40488J | | E | | D40490P | 4 | | | 115-199 |
| 0006 | 20 | GA | | | 23-0 | 33-51-11 | D40488J | | F | | D40490P | 5 | | | 001-099 |
| 0006 | 18 | GA | | | 14-0 | 33-51-11 | D40488J | | F | | D40490P | 5 | | | 115-199 |
| 0007 | 18 | GA | | | 14-0 | 33-42-12 | D40488J | | G | | D40490P | 6 | | | 115-199 |
| 0008 | 12 | GA | | | 9-0 | 33-42-12 | D40488J | | P | | GD00028 | ST.. | E | | 115-199 |
| 0009 | 20 | GA | | | 42-0 | 23-43-11 | D40488J | | H | | TB0116X | A015 | BJ | | ALL |
| 0010 | 20 | GA | | | 42-0 | 23-43-11 | D40488J | | I | | TB0116X | B015 | BJ | | ALL |
| 0011 | 16 | GA | | | 7-0 | 33-42-21 | D40488J | | L | | GD00027 | AC.. | E | | 001-099 |
| 0011 | 16 | GA | | | 9-0 | 33-42-21 | D40488J | | L | | GD00027 | AC.. | E | | 115-199 |
| 0012 | 12 | GA | | | 8-0 | 33-42-12 | D40488J | | R | | GD00027 | AC.. | E | | 115-199 |
| 0013 | 20 | GA | | | 7-0 | 33-51-11 | D40488J | | C- | | GD00029 | DC.. | E | | 001-099 |
| 0013 | 18 | GA | | | 9-0 | 33-51-11 | D40488J | | C- | | GD00029 | DC.. | E | | 115-199 |
| 2001B | 20 | GB | AA | | 39-0 | 32-61-13 | SP00026 | | | 9 | D41646P | 1 | | | 001-099 |
| 2001B | 20 | GB | AA | | 41-0 | 32-61-13 | SP00026 | | | 9 | D41646P | 1 | | | 115-199 |
| 2001R | 20 | GB | AA | | 0-0 | 32-61-13 | SP00024 | | | 9 | D41646P | 2 | | | ALL |
| 2002B | 20 | GB | AB | | 31-0 | 32-61-22 | SP00030 | | | 9 | D41646P | 3 | | | 001-099 |
| 2002B | 20 | GB | AB | | 33-0 | 32-61-22 | SP00030 | | | 9 | D41646P | 3 | | | 115-199 |
| 2002R | 20 | GB | AB | | 0-0 | 32-61-22 | SP00028 | | | 9 | D41646P | 4 | | | ALL |
| 2003B | 20 | GB | AC | | 34-0 | 32-61-22 | SP00034 | | | 9 | D41646P | 5 | | | 001-099 |
| 2003B | 20 | GB | AC | | 43-0 | 32-61-22 | SP00034 | | | 9 | D41646P | 5 | | | 115-199 |
| 2003R | 20 | GB | AC | | 0-0 | 32-61-22 | SP00032 | | | 9 | D41646P | 6 | | | ALL |
| 2004B | 20 | GB | AD | | 34-0 | 32-61-13 | SP00038 | | | 9 | D41646P | 7 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2050

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|---|-------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2052 | 286N2052 | P37,E/E BAY TO NOSE GEAR WHEELWELL DISC. (continued) | | | | | | | | | | | | | |
| 2004B | 20 | GB | AD | 43-0 | 32-61-13 | SP00038 | | 9 | D41646P | 7 | | | 115-199 | | |
| 2004R | 20 | GB | AD | 0-0 | 32-61-13 | SP00036 | | 9 | D41646P | 8 | | | ALL | | |
| 2005B | 20 | GB | AE | 31-0 | 32-09-12 | D40488J | K | | D41646P | 9 | | | 001-099 | | |
| 2005B | 18 | GB | AE | 33-0 | 32-09-12 | D40488J | K | | D41646P | 9 | | | 115-199 | | |
| 2005R | 20 | GB | AE | 0-0 | 32-09-12 | D40488J | J | | D41646P | 10 | | | 001-099 | | |
| 2005R | 18 | GB | AE | 0-0 | 32-09-12 | D40488J | J | | D41646P | 10 | | | 115-199 | | |
| 2501B | 20 | GU | AH | 28-0 | 23-41-12 | D40488J | M | | D41648P | 1 | | | 001-099 | | |
| 2501R | 20 | GU | AH | 0-0 | 23-41-12 | D40488J | N | | D41648P | 2 | | | 001-099 | | |
| 2501Z | | | AH | 0-0 | 23-41-12 | D40488J | X | | D41648P | 4 | | | 001-099 | | |
| 3501B | 20 | GV | AF | 28-0 | 23-41-12 | D40488J | M | | D41648P | 1 | | | 115-199 | | |
| 3501R | 20 | GV | AF | 0-0 | 23-41-12 | D40488J | N | | D41648P | 2 | | | 115-199 | | |
| 3501Y | 20 | GV | AF | 0-0 | 23-41-12 | D40488J | W | | D41648P | 3 | | | 115-199 | | |
| 3501Z | | | AF | 0-0 | 23-41-12 | D40488J | X | | D41648P | 4 | | | 115-199 | | |
| 3502B | 20 | GV | AG | 28-0 | 23-51-13 | D40488J | Z | | D41648P | 5 | | | ALL | | |
| 3502R | 20 | GV | AG | 0-0 | 23-51-13 | D40488J | Y | | D41648P | 6 | | | ALL | | |
| 3502Y | 20 | GV | AG | 0-0 | 23-51-13 | D40488J | A- | | D41648P | 7 | | | ALL | | |
| 3502Z | | | AG | 0-0 | 23-51-13 | D40488J | B- | | D41648P | 8 | | | ALL | | |
| A-A | | | | 0-0 | 32-61-13 | S10077 | BLU | | SP00038 | | 9 | | ALL | | |
| A-B | | | | 0-0 | 32-61-13 | S10077 | RED | | SP00036 | | 9 | | ALL | | |
| A-C | | | | 0-0 | 32-61-22 | S10078 | BLU | | SP00030 | | 9 | | ALL | | |
| A-D | | | | 0-0 | 32-61-22 | S10078 | RED | | SP00028 | | 9 | | ALL | | |
| A-E | | | | 0-0 | 32-61-22 | S10079 | BLU | | SP00034 | | 9 | | ALL | | |
| A-F | | | | 0-0 | 32-61-22 | S10079 | RED | | SP00032 | | 9 | | ALL | | |
| A-G | | | | 0-0 | 32-61-13 | S10081 | BLU | | SP00026 | | 9 | | ALL | | |
| A-H | | | | 0-0 | 32-61-13 | S10081 | RED | | SP00024 | | 9 | | ALL | | |
| W2054 | 286N2054 | P36 TO L. AUX PITOT PROBE | | | | | | | | | | | | | |
| 0001 | 20 | GA | | 42-0 | 30-31-11 | D40860P | | 1 | D02758 | = A | | | 115-199 | | |
| 0002 | 20 | GA | | 42-0 | 30-31-11 | D40860P | | 2 | D02758 | = B | | | 115-199 | | |
| W2055 | 286N2055 | RIGHT STICK SHAKER | | | | | | | | | | | | | |
| 0001 | 22 | 6A | | 5-0 | 27-32-21 | D00489 | | A | SP00185 | | 9 | | ALL | | |
| 0002 | 22 | 6A | | 5-0 | 27-32-21 | D00489 | | B | SP00187 | | 9 | | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W2050

Page 4 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2061 | 286N2061 | | | | P55 GLARE SHIELD-M90 CONTROL PANEL TO AP0001 | | | | | | | | | | | | |
| 0001 | 22 | | GA | | 10-0 | 22-11-32 | | D00057 | | 7 | | D40633P | | 4 | | ALL | |
| 0002 | 22 | | GA | | 10-0 | 22-11-32 | | D00057 | | 30 | | D40633P | | 5 | | ALL | |
| 0003 | 22 | | GA | | 10-0 | 22-11-32 | | D00057 | | 22 | | D40633P | | 6 | | 115-199 | |
| 0004 | 20 | | GA | | 11-0 | 22-11-32 | | D00057 | | 19 | | GD01009 | ST.. | 2 | | ALL | |
| 0005 | 20 | | GA | | 11-0 | 22-11-32 | | D00057 | | 18 | | GD01009 | DC.. | 2 | | ALL | |
| 0006 | 20 | | GA | | 5-0 | 33-13-41 | | D00057 | | 4 | | SP00213 | | W | | ALL | |
| 0007 | 20 | | GA | | 11-0 | 33-13-41 | | D00057 | | 1 | | GD01009 | AC.. | 2 | | ALL | |
| 0009 | 22 | | GA | | 10-0 | SPARE | | D00057 | | 9 | | D40633P | | 7 | | 115-199 | |
| 0010 | 22 | | GA | | 10-0 | SPARE | | D00057 | | 10 | | D40633P | | 8 | | 115-199 | |
| 5001B | 24 | | G2 | AA | 10-0 | 22-12-31 | | D00057 | | 21 | | D40633P | | 2 | | ALL | |
| 5001R | 24 | | G2 | AA | 0-0 | 22-12-31 | | D00057 | | 20 | | D40633P | | 1 | | ALL | |
| 5001Z | | | | AA | 0-0 | 22-12-31 | | GD02711 | ST.. | E | | D40633P | | 3 | | ALL | |
| W2064 | 286N2064 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM | | | | | | | | | | | | |
| 0001 | 24 | | GK | | 29-0 | 30-31-11 | | D03564 | | 1 | | D41410P | | 3 | | ALL | |
| 0003 | 22 | | GA | | 38-0 | 30-41-11 | | D41874P | | 23 | | TB0112X | D016 | BJ | | ALL | |
| 0005 | 20 | | GA | | 27-0 | 33-42-11 | | D41410P | | 11 | | D40582P | | 32 | | 001-099 | |
| 0005 | 20 | | GA | | 26-0 | 33-42-11 | | D41410P | | 11 | | D40582P | | 32 | | 115-199 | |
| 0018 | 24 | | GK | | 29-0 | 30-32-11 | | D03564 | | 8 | | D41410P | | 31 | | ALL | |
| 0029 | 20 | | GA | | 20-0 | 33-44-21 | | D41410P | | 4 | | D41852P | | 1 | | 001-099 | |
| 0029 | 20 | | GA | | 19-0 | 33-44-21 | | D41852P | | 1 | | D41410P | | 4 | | 115-199 | |
| 0032 | 20 | | GA | | 30-0 | 33-42-11 | | D03505 | | 10 | | D41410P | | 5 | | 001-099 | |
| 0032 | 20 | | GA | | 29-0 | 33-42-11 | | D03505 | | 12 | | D41410P | | 5 | | 115-199 | |
| 0033 | 20 | | GA | | 30-0 | 33-42-11 | | D03505 | | 15 | | D41410P | | 6 | | 001-099 | |
| 0033 | 20 | | GA | | 29-0 | 33-42-11 | | D03505 | | 3 | | D41410P | | 6 | | 115-199 | |
| 0034 | 20 | | GA | | 7-0 | 33-42-12 | | D03505 | | 13 | | D40798J | | 7 | | 001-099 | |
| 0035 | 20 | | GA | | 30-0 | 33-42-12 | | D03505 | | 14 | | D41410P | | 25 | | 001-099 | |
| 0036 | 22 | | GA | | 27-0 | SPARE | | D41410P | | 28 | | D40582P | | 36 | | 001-099 | |
| 0037 | 22 | | GA | | 27-0 | SPARE | | D41410P | | 30 | | D40582P | | 37 | | 001-099 | |
| 0038 | 20 | | GA | | 27-0 | 33-42-12 | | D41410P | | 18 | | D40582P | | 40 | | 001-099 | |
| 0040 | 24 | | GK | | 47-0 | 30-33-11 | | D03564 | | 3 | | D41840P | | 1 | | ALL | |
| 0042 | 20 | | GA | | 4-0 | 30-41-11 | | D03552 | | 5 | | GD00609 | AC.. | 2 | | ALL | |
| 0043 | 20 | | GA | | 4-0 | 30-41-11 | | D03552 | | 6 | | GD00609 | AC.. | 2 | | ALL | |
| 0044 | 22 | | GA | | 46-0 | 30-41-11 | | D03552 | | 7 | | D41840P | | 2 | | 001-099 | |
| 0044 | 22 | | GA | | 45-0 | 30-41-11 | | D03552 | | 7 | | D41840P | | 2 | | 115-199 | |
| 0054 | 20 | | GA | | 65-0 | 21-45-11 | | D40582P | | 1 | | SM00001 | | 9 | | 001-099 | |
| 0054 | 20 | | GA | | 64-0 | 21-45-11 | | D40582P | | 1 | | SM00001 | | 9 | | 115-199 | |
| 0055 | 20 | | GA | | 65-0 | 21-45-11 | | D03152 | | 7 | | D40582P | | 2 | | ALL | |
| 0058 | 22 | | GA | | 46-0 | 30-41-11 | | D03552 | | 8 | | D41840P | | 3 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity | | | | | | | | |
|------------|-------------|--|-------|----------|-------------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2064 | 286N2064 | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0058 | 22 | GA | 45-0 | 30-41-11 | D03552 | 8 | | | D41840P | 3 | | | 115-199 |
| 0059 | 20 | GA | 65-0 | 21-45-11 | D03152 | 8 | | | D40582P | 3 | | | ALL |
| 0060 | 20 | GA | 5-0 | 21-45-11 | D03152 | 3 | | | GD01017 | AC.. | 2 | | ALL |
| 0061 | 20 | GA | 4-0 | 21-45-11 | D03152 | 10 | | | SM00002 | | 9 | | ALL |
| 0062 | 20 | GA | 4-0 | 21-45-11 | D02720 | 1 | | | SM00002 | | 9 | | ALL |
| 0063 | 20 | GA | 4-0 | 21-45-11 | D02720 | 2 | | | SM00001 | | 9 | | ALL |
| 0068 | 20 | GA | 3-0 | 21-45-11 | D02720 | 3 | | | GD01727 | ST.. | E | | ALL |
| 0069 | 20 | GA | 51-0 | 21-45-11 | D01582 | 1 | | | D03152 | 4 | | | 001-099 |
| 0069 | 20 | GA | 50-0 | 21-45-11 | D01582 | 1 | | | D03152 | 4 | | | 115-199 |
| 0070 | 20 | GA | 50-0 | 21-45-11 | D01582 | 2 | | | SM00001 | | 9 | | ALL |
| 0071 | 20 | GA | 3-0 | 21-45-11 | D01582 | 3 | | | GD01260 | ST.. | E | | ALL |
| 0072 | 20 | GA | 3-0 | 21-45-11 | D01580 | 1 | | | SM00002 | | 9 | | ALL |
| 0073 | 20 | GA | 3-0 | 21-45-11 | D01580 | 2 | | | SM00001 | | 9 | | ALL |
| 0074 | 20 | GA | 2-0 | 21-45-11 | D01580 | 3 | | | GD01727 | ST.. | E | | ALL |
| 0075 | 24 | GK | 40-0 | 21-25-11 | D40798J | 5 | | | D41852P | 18 | | | ALL |
| 0078 | 20 | GA | 8-0 | 33-43-12 | TB0114X | A024 | BJ | | D03505 | 19 | | | 001-099 |
| 0078 | 20 | GA | 8-0 | 33-43-12 | TB0114X | A024 | BJ | | D03505 | 8 | | | 115-199 |
| 0079 | 20 | GA | 40-0 | 33-43-12 | D03505 | 18 | | | D41852P | 6 | | | 001-099 |
| 0079 | 20 | GA | 40-0 | 33-43-12 | D03505 | 7 | | | D41852P | 6 | | | 115-199 |
| 0087 | 24 | GK | 18-0 | SPARE | D40582P | 6 | | | D41840P | 11 | | | 001-099 |
| 0087 | 24 | GK | 18-0 | 21-58-24 | D40582P | 6 | | | D41840P | 11 | | | 115-199 |
| 0088 | 24 | GK | 23-0 | 21-61-11 | D41840P | 10 | | | D41852P | 3 | | | ALL |
| 0089 | 22 | GA | 30-0 | SPARE | D40798J | 19 | | | D41410P | 15 | | | 001-099 |
| 0089 | 22 | GA | 29-0 | 32-09-11 | D40798J | 19 | | | D41410P | 15 | | | 115-199 |
| 0091 | 20 | GA | 5-0 | 33-13-11 | D03152 | 1 | | | D41846J | 8 | | | ALL |
| 0092 | 20 | GA | 5-0 | 33-13-11 | D03152 | 2 | | | GD01017 | AC.. | 2 | | ALL |
| 0105 | 22 | GA | 39-0 | 30-41-11 | D03552 | 11 | | | D41874P | 5 | | | ALL |
| 0106 | 22 | GA | 39-0 | 30-41-11 | D03552 | 9 | | | D41874P | 6 | | | ALL |
| 0107 | 22 | GA | 39-0 | 30-41-11 | D03552 | 12 | | | D41874P | 7 | | | ALL |
| 0108 | 22 | GA | 39-0 | 30-41-11 | D03552 | 10 | | | D41874P | 8 | | | ALL |
| 0112 | 24 | GK | 47-0 | SPARE | D40798J | 10 | | | D40582P | 43 | | | 001-099 |
| 0114 | 22 | GA | 30-0 | 29-11-11 | D40798J | 35 | | | D41410P | 27 | | | 001-099 |
| 0114 | 22 | GA | 29-0 | 29-11-11 | D40798J | 35 | | | D41410P | 27 | | | 115-199 |
| 0127 | 22 | GA | 41-0 | 27-23-11 | D03712 | 11 | | | D40582P | 33 | | | 001-099 |
| 0127 | 22 | GA | 40-0 | 27-23-11 | D03712 | 11 | | | D40582P | 33 | | | 115-199 |
| 0128 | 22 | GA | 41-0 | 27-23-11 | D03712 | 6 | | | D40582P | 34 | | | 001-099 |
| 0128 | 22 | GA | 40-0 | 27-23-11 | D03712 | 6 | | | D40582P | 34 | | | 115-199 |
| 0129 | 22 | GA | 41-0 | 27-23-11 | D03712 | 5 | | | D40582P | 35 | | | 001-099 |
| 0129 | 22 | GA | 40-0 | 27-23-11 | D03712 | 5 | | | D40582P | 35 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2064 | 286N2064 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0130 | 22 | | GA | | 14-0 | 33-16-22 | | D03712 | | 3 | | TB0112X | A003 | BJ | | ALL |
| 0131 | 22 | | GA | | 7-0 | 33-16-13 | | D03712 | | 4 | | TB0121Z | 15 | BJ | | ALL |
| 0144 | 20 | | GA | | 7-0 | 23-11-11 | | D40798J | | 9 | | TB0111X | A001 | BJ | | 001-099 |
| 0144 | 20 | | GA | | 7-0 | 23-11-11 | | D40798J | | 7 | | TB0111X | A001 | BJ | | 115-199 |
| 0145 | 22 | | GA | | 30-0 | 34-53-11 | | D40798J | | 12 | | TB0059Y | A011 | BJ | | ALL |
| 0148 | 22 | | GA | | 41-0 | 30-41-11 | | D40798J | | 28 | | D41874P | 2 | | | ALL |
| 0149 | 20 | | GA | | 18-0 | 29-11-22 | | D40582P | | 4 | | D41840P | 4 | | | ALL |
| 0150 | 24 | | GK | | 18-0 | SPARE | | D40582P | | 5 | | D41840P | 5 | | | 001-099 |
| 0150 | 24 | | GK | | 18-0 | 21-58-24 | | D40582P | | 5 | | D41840P | 5 | | | 115-199 |
| 0151 | 20 | | GA | | 18-0 | SPARE | | D40582P | | 7 | | D41840P | 6 | | | 115-199 |
| 0152 | 20 | | GA | | 65-0 | SPARE | | D40582P | | 8 | | D41846J | 3 | | | 001-099 |
| 0152 | 20 | | GA | | 18-0 | SPARE | | D40582P | | 8 | | D41840P | 7 | | | 115-199 |
| 0153 | 20 | | GA | | 65-0 | SPARE | | D40582P | | 11 | | D41846J | 4 | | | 001-099 |
| 0153 | 20 | | GA | | 18-0 | SPARE | | D40582P | | 11 | | D41840P | 8 | | | 115-199 |
| 0154 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 13 | | D41852P | 4 | | | 115-199 |
| 0155 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 14 | | D41852P | 5 | | | 115-199 |
| 0156 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 16 | | D41852P | 7 | | | 115-199 |
| 0157 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 17 | | D41852P | 8 | | | 115-199 |
| 0158 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 18 | | D41852P | 9 | | | 115-199 |
| 0159 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 19 | | D41852P | 10 | | | 115-199 |
| 0160 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 20 | | D41852P | 11 | | | 115-199 |
| 0161 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 21 | | D41852P | 12 | | | 115-199 |
| 0162 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 22 | | D41852P | 13 | | | 115-199 |
| 0163 | 20 | | GA | | 22-0 | SPARE | | D40582P | | 23 | | D41852P | 14 | | | 115-199 |
| 0164 | 24 | | GK | | 27-0 | 27-51-31 | | D40582P | | 24 | | D41410P | 9 | | | 001-099 |
| 0164 | 20 | | GA | | 26-0 | 27-51-31 | | D40582P | | 24 | | D41410P | 9 | | | 115-199 |
| 0165 | 20 | | GA | | 27-0 | 30-32-11 | | D40582P | | 25 | | D41410P | 10 | | | 001-099 |
| 0165 | 20 | | GA | | 26-0 | 30-32-11 | | D40582P | | 25 | | D41410P | 10 | | | 115-199 |
| 0166 | 20 | | GA | | 65-0 | SPARE | | D40582P | | 26 | | D41846J | 5 | | | 001-099 |
| 0166 | 20 | | GA | | 26-0 | SPARE | | D40582P | | 26 | | D41410P | 13 | | | 115-199 |
| 0167 | 20 | | GA | | 65-0 | SPARE | | D40582P | | 27 | | D41846J | 6 | | | 001-099 |
| 0167 | 20 | | GA | | 26-0 | SPARE | | D40582P | | 27 | | D41410P | 16 | | | 115-199 |
| 0168 | 18 | | GA | | 27-0 | 28-22-11 | | D40582P | | 28 | 18 | D41410P | 21 | | | 001-099 |
| 0168 | 18 | | GA | | 26-0 | 28-22-11 | | D40582P | | 28 | 18 | D41410P | 17 | 18 | | 115-199 |
| 0169 | 18 | | GA | | 27-0 | 28-22-11 | | D40582P | | 42 | 18 | D41410P | 23 | | | 001-099 |
| 0169 | 18 | | GA | | 26-0 | 28-22-11 | | D40582P | | 29 | 18 | D41410P | 18 | 18 | | 115-199 |
| 0170 | 20 | | GA | | 20-0 | SPARE | | D41852P | | 21 | | D41410P | 19 | | | 001-099 |
| 0170 | 20 | | GA | | 19-0 | SPARE | | D41852P | | 21 | | D41410P | 19 | | | 115-199 |
| 0171 | 20 | | GA | | 20-0 | SPARE | | D41852P | | 22 | | D41410P | 20 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2064 | 286N2064 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0171 | 20 | GA | | 19-0 | SPARE | D41852P | 22 | | | | D41410P | 20 | | | 115-199 |
| 0172 | 20 | GA | | 20-0 | SPARE | D41852P | 23 | | | | D41410P | 17 | | | 001-099 |
| 0172 | 20 | GA | | 19-0 | SPARE | D41852P | 23 | | | | D41410P | 21 | | | 115-199 |
| 0173 | 20 | GA | | 65-0 | SPARE | D40582P | 16 | | | | D41846J | 7 | | | 001-099 |
| 0173 | 20 | GA | | 19-0 | SPARE | D41852P | 24 | | | | D41410P | 22 | | | 115-199 |
| 0174 | 20 | GA | | 19-0 | SPARE | D41852P | 25 | | | | D41410P | 23 | | | 115-199 |
| 0175 | 20 | GA | | 19-0 | SPARE | D41852P | 26 | | | | D41410P | 24 | | | 115-199 |
| 0176 | 20 | GA | | 29-0 | SPARE | D03505 | | CAP | Y | | D41410P | 25 | | | 115-199 |
| 0177 | 20 | GA | | 30-0 | SPARE | D03505 | | CAP | Y | | D41410P | 26 | | | 001-099 |
| 0177 | 20 | GA | | 29-0 | SPARE | D03505 | | CAP | Y | | D41410P | 26 | | | 115-199 |
| 0178 | 20 | GA | | 47-0 | SPARE | D03505 | | CAP | Y | | D40582P | 30 | | | ALL |
| 0179 | 20 | GA | | 47-0 | SPARE | D03505 | | CAP | Y | | D40582P | 31 | | | ALL |
| 0180 | 22 | GA | | 5-0 | 32-42-11 | D40798J | 14 | | | | TB0113A | A023 | 2 | | 001-099 |
| 0181 | 22 | GA | | 46-0 | 32-42-11 | D40582P | 48 | | | | TB0113A | C023 | 2 | | 001-099 |
| 0182 | 22 | GA | | 22-0 | 32-42-12 | D41846J | 9 | | | | TB0113A | C024 | 2 | | 001-099 |
| 0183 | 22 | GA | | 1-0 | 32-42-12 | TB0113A | | C023 | 2 | | TB0113A | C024 | 2 | | 001-099 |
| 0185 | 22 | GA | | 22-0 | 30-34-21 | D40582P | 38 | | | | D41852P | 27 | | | ALL |
| 0186 | 22 | GA | | 23-0 | 30-34-21 | D41840P | 9 | | | | D41852P | 28 | | | ALL |
| 0187 | 22 | GA | | 22-0 | 30-34-21 | D40582P | 29 | | | | D41852P | 29 | | | 001-099 |
| 0187 | 22 | GA | | 22-0 | 30-34-21 | D40582P | 36 | | | | D41852P | 29 | | | 115-199 |
| 0188 | 20 | GA | | 40-0 | SPARE | D03505 | | CAP | Y | | D41852P | 15 | | | ALL |
| 0189 | 20 | GA | | 40-0 | SPARE | D03505 | | CAP | Y | | D41852P | 16 | | | ALL |
| 0190 | 22 | GA | | 30-0 | 34-57-11 | D40798J | 3 | | | | TB0059X | C009 | BJ | | 001-099 |
| 0190 | 20 | GA | | 30-0 | 34-57-11 | D40798J | 3 | | | | TB0059X | C009 | BJ | | 115-199 |
| 0192 | 22 | GA | | 47-0 | SPARE | D40582P | 39 | | | | D40798J | 8 | | | 001-099 |
| 0218 | 22 | GA | | 7-0 | 33-16-12 | D03564 | 5 | | | | TB0112Z | 7 | BJ | | ALL |
| 0223 | 22 | GA | | 5-0 | 33-16-12 | D03552 | 4 | | | | TB0112Z | 8 | BJ | | ALL |
| 0227 | 22 | GA | | 1-0 | 33-16-12 | TB0112Z | 6 | | BJ | | TB0112Z | 5 | BJ | | ALL |
| 0228 | 22 | GA | | 2-0 | 33-16-12 | TB0112Z | 8 | | BJ | | TB0112Z | 7 | BJ | | ALL |
| 0242 | 20 | GA | | 7-0 | 33-44-21 | D40798J | 6 | | | | D03505 | 5 | | | ALL |
| 0243 | 20 | GA | | 40-0 | 33-44-21 | D03505 | 6 | | | | D41852P | 2 | | | ALL |
| 0246 | 22 | GA | | 5-0 | 33-16-22 | D03552 | 3 | | | | TB0112Y | C009 | BJ | | ALL |
| 0247 | 22 | GA | | 7-0 | 33-16-22 | D03564 | 6 | | | | TB0112Y | C009 | BJ | | ALL |
| 0260 | 20 | GA | | 27-0 | SPARE | D41410P | 1 | | | | D40582P | 15 | | | 001-099 |
| 0260 | 20 | GA | | 26-0 | SPARE | D41410P | 1 | | | | D40582P | 15 | | | 115-199 |
| 0261 | 20 | GA | | 27-0 | SPARE | D41410P | 2 | | | | D40582P | 12 | | | 001-099 |
| 0261 | 20 | GA | | 26-0 | SPARE | D41410P | 2 | | | | D40582P | 12 | | | 115-199 |
| 0297 | 20 | GA | | 7-0 | 33-42-11 | D40798J | 17 | | | | D03505 | 11 | | | ALL |
| 0298 | 20 | GA | | 7-0 | 33-42-11 | D40798J | 18 | | | | D03505 | 12 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2064 | 286N2064 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | | |
| 0298 | 20 | | GA | | 7-0 | 33-42-11 | | D40798J | 18 | | | D03505 | 4 | | | 115-199 | |
| 0299 | 24 | | GK | | 27-0 | 34-12-12 | | D40582P | 10 | | | D41410P | 8 | | | 001-099 | |
| 0299 | 24 | | GK | | 26-0 | 34-12-12 | | D40582P | 10 | | | D41410P | 8 | | | 115-199 | |
| 0301 | 22 | | GA | | 21-0 | 30-43-11 | | TB0115X | D002 | BJ | | D41846J | 10 | | | ALL | |
| 0302 | 20 | | GA | | 8-0 | 33-13-31 | | TB0114Z | 11 | BJ | | D03505 | 1 | | | ALL | |
| 0303 | 20 | | GA | | 8-0 | 33-13-31 | | TB0114Z | 12 | BJ | | D03505 | 2 | | | ALL | |
| 0306 | 20 | | GA | | 5-0 | 33-13-31 | | TB0114Z | 7 | BJ | | D03552 | 1 | | | ALL | |
| 0307 | 20 | | GA | | 5-0 | 33-13-31 | | TB0114Z | 9 | BJ | | D03552 | 2 | | | ALL | |
| 0319 | 24 | | GK | | 27-0 | 34-12-12 | | D41410P | 7 | | | D40582P | 9 | | | 001-099 | |
| 0319 | 24 | | GK | | 26-0 | 34-12-12 | | D41410P | 7 | | | D40582P | 9 | | | 115-199 | |
| 0320 | 18 | | GA | | 8-0 | 30-42-11 | | D40798J | 23 | | | D03522 | 7 | | | ALL | |
| 0322 | 22 | | GA | | 8-0 | 33-14-41 | | TB0114X | B014 | BJ | | D40798J | 13 | | | ALL | |
| 0323 | 22 | | GA | | 8-0 | 30-43-11 | | D40798J | 21 | | | D03522 | 8 | | | ALL | |
| 0324 | 22 | | GA | | 8-0 | 30-43-11 | | D03522 | 9 | | | TB0114X | C014 | BJ | | ALL | |
| 0325 | 24 | | GK | | 29-0 | 30-31-11 | | D03564 | 2 | | | D41410P | 12 | | | ALL | |
| 0326 | 18 | | GA | | 25-0 | 30-42-11 | | D03522 | 10 | | | D41846J | 21 | | | ALL | |
| 0328 | 18 | | GA | | 25-0 | 30-42-11 | | D03522 | 4 | | | D41846J | 23 | | | ALL | |
| 0333 | 22 | | GA | | 17-0 | 27-23-11 | | D40798J | 1 | | | D03712 | 7 | | | ALL | |
| 0334 | 22 | | GA | | 41-0 | 30-41-11 | | D41874P | 9 | | | TB0111X | B002 | BJ | | ALL | |
| 0337 | 22 | | GA | | 58-0 | 29-21-32 | | D41846J | 1 | | | D41852P | 30 | | | ALL | |
| 0338 | 22 | | GA | | 58-0 | 29-21-32 | | D41846J | 2 | | | D41852P | 31 | | | ALL | |
| 0800 | 24 | | GK | | 47-0 | 34-22-83 | | D41846J | 5 | | | TB0059X | D008 | BJ | | 115-199 | |
| 0801 | 22 | | GA | | 24-0 | 34-55-11 | | D40798J | 20 | | | D41846J | 20 | | | 115-199 | |
| 2010B | 22 | | GB | AB | 7-0 | 29-11-31 | | TB0121X | C004 | BJ | | D03712 | 1 | | | 115-199 | |
| 2010R | 22 | | GB | AB | 0-0 | 29-11-31 | | TB0121X | D004 | BJ | | D03712 | 2 | | | 115-199 | |
| W2066 | 286N2066 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM | | | | | | | | | | | | |
| 0001 | 24 | | GK | | 20-0 | 33-13-51 | | D40800J | 12 | | | SM00001 | 9 | | | 001-099 | |
| 0001 | 24 | | GK | | 22-0 | 33-13-51 | | D40800J | 12 | | | SM00001 | 9 | | | 115-199 | |
| 0002 | 24 | | GK | | 8-0 | 33-13-71 | | D40800J | 14 | | | TB0114Y | C005 | BJ | | 115-199 | |
| 0003 | 22 | | GA | | 27-0 | 33-11-11 | | D40800J | 31 | | | D41170J | 5 | | | ALL | |
| 0004 | 24 | | GK | | 46-0 | 21-31-11 | | D02344 | 7 | | | D41864P | 6 | | | ALL | |
| 0005 | 24 | | GK | | 46-0 | 21-31-11 | | D02344 | 30 | | | D41864P | 7 | | | ALL | |
| 0006 | 24 | | GK | | 46-0 | 21-31-11 | | D02344 | 19 | | | D41864P | 8 | | | ALL | |
| 0007 | 20 | | GA | | 46-0 | 21-31-11 | | D02344 | 16 | | | D41864P | 9 | | | ALL | |
| 0008 | 22 | | GA | | 42-0 | SPARE | | D40800J | 42 | | | D40972P | 16 | | | ALL | |
| 0009 | 20 | | GA | | 5-0 | 33-13-52 | | D06488 | 2 | | | TB0058Z | 3 | BJ | | ALL | |
| 0010 | 24 | | GK | | 13-0 | 33-13-51 | | D02892 | 12 | | | SM00001 | 9 | | | 001-099 | |
| 0010 | 24 | | GK | | 11-0 | 33-13-51 | | D02892 | 12 | | | SM00001 | 9 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | | 286N2066 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | |
| 0011 | 22 | GA | | | 39-0 | 27-23-11 | D03708 | | 13 | | D40584P | | 13 | | 001-099 |
| 0011 | 22 | GA | | | 38-0 | 27-23-11 | D03708 | | 13 | | D40584P | | 13 | | 115-199 |
| 0012 | 22 | GA | | | 41-0 | 27-28-13 | GD01650 | AC.. | 2 | *2 | D40584P | | 14 | | 001-099 |
| 0012 | 22 | GA | | | 40-0 | 27-28-13 | GD01650 | AC.. | 2 | *2 | D40584P | | 14 | | 115-199 |
| 0013 | 24 | GK | | | 44-0 | 36-22-11 | D03538 | | 22 | | D40584P | | 39 | | ALL |
| 0014 | 16 | GA | | | 5-0 | 33-13-51 | D02892 | | 11 | 16 | GD00109 | AC.. | 2 | | 001-099 |
| 0014 | 16 | GA | | | 4-0 | 33-13-51 | D02892 | | 11 | 16 | GD00109 | AC.. | 2 | | 115-199 |
| 0015 | 20 | GA | | | 5-0 | 33-13-51 | D02892 | | 7 | | GD00109 | ST.. | 2 | | 001-099 |
| 0015 | 20 | GA | | | 4-0 | 33-13-51 | D02892 | | 7 | | GD00109 | ST.. | 2 | | 115-199 |
| 0016 | 22 | GA | | | 12-0 | 33-16-12 | TB0112Z | | 5 | BJ | D41000P | | 11 | | ALL |
| 0017 | 24 | GK | | | 43-0 | 21-25-11 | TB0112Y | A010 | BJ | | D40584P | | 22 | | ALL |
| 0018 | 22 | GA | | | 7-0 | 34-12-12 | D03702 | | 4 | | GD00620 | DC.. | 2 | | ALL |
| 0019 | 20 | GA | | | 7-0 | 33-13-51 | D02892 | | 9 | | TB0100Y | A005 | BJ | | 001-099 |
| 0019 | 20 | GA | | | 4-0 | 33-13-51 | D02892 | | 9 | | TB0100Y | A005 | BJ | | 115-199 |
| 0020 | 24 | GK | | | 41-0 | 24-11-11 | D03708 | | 5 | | D41864P | | 25 | | 001-099 |
| 0020 | 24 | GK | | | 40-0 | 24-11-11 | D03708 | | 5 | | D41864P | | 25 | | 115-199 |
| 0021 | 22 | GA | | | 47-0 | 24-11-11 | D03500 | | 13 | | D41864P | | 23 | | 001-099 |
| 0021 | 22 | GA | | | 46-0 | 24-11-11 | D03500 | | 13 | | D41864P | | 23 | | 115-199 |
| 0022 | 22 | GA | | | 30-0 | 24-22-11 | D03500 | | 18 | | TB0058X | C007 | BJ | | ALL |
| 0023 | 22 | GA | | | 43-0 | 24-22-11 | TB0058X | D007 | BJ | | D41864P | | 18 | | 001-099 |
| 0023 | 22 | GA | | | 42-0 | 24-22-11 | TB0058X | D007 | BJ | | D41864P | | 18 | | 115-199 |
| 0024 | 16 | GA | | | 20-0 | 33-13-51 | D02892 | | 8 | 16 | TB0158F | A010 | 2 | | 001-099 |
| 0024 | 16 | GA | | | 21-0 | 33-13-51 | D02892 | | 8 | 16 | TB0158F | A010 | 2 | | 115-199 |
| 0025 | 24 | GK | | | 15-0 | 33-13-52 | D02890 | | 12 | | SM00001 | | 9 | | 001-099 |
| 0025 | 24 | GK | | | 13-0 | 33-13-52 | D02890 | | 12 | | SM00001 | | 9 | | 115-199 |
| 0026 | 22 | GA | | | 17-0 | 24-22-11 | D03708 | | 8 | | D03500 | | 20 | | ALL |
| 0027 | 22 | GA | | | 41-0 | 24-22-11 | D03708 | | 7 | | D41864P | | 20 | | 001-003 |
| 0027 | 22 | GA | | | 40-0 | 24-22-11 | D03708 | | 7 | | D41864P | | 20 | | 115-199 |
| 0028 | 22 | GA | | | 41-0 | 24-22-11 | D03708 | | 9 | | D41864P | | 21 | | 001-003 |
| 0028 | 22 | GA | | | 40-0 | 24-22-11 | D03708 | | 9 | | D41864P | | 21 | | 115-199 |
| 0029 | 22 | GA | | | 47-0 | 24-22-11 | D03500 | | 21 | | D41864P | | 10 | | 001-099 |
| 0029 | 22 | GA | | | 46-0 | 24-22-11 | D03500 | | 21 | | D41864P | | 10 | | 115-199 |
| 0030 | 22 | GA | | | 47-0 | 24-22-11 | D03500 | | 19 | | D41864P | | 11 | | 001-099 |
| 0030 | 22 | GA | | | 46-0 | 24-22-11 | D03500 | | 19 | | D41864P | | 11 | | 115-199 |
| 0031 | 20 | GA | | | 7-0 | 33-13-52 | D02890 | | 7 | | GD02316 | ST.. | 2 | | ALL |
| 0032 | 24 | GK | | | 23-0 | 21-43-11 | D40584P | | 32 | | D42074P | | 5 | | ALL |
| 0033 | 24 | GK | | | 45-0 | 24-27-11 | D03500 | | 26 | | D40584P | | 33 | | ALL |
| 0034 | 24 | GK | | | 45-0 | 24-27-11 | D03500 | | 25 | | D40584P | | 34 | | ALL |
| 0035 | 24 | GK | | | 45-0 | 24-27-11 | D03500 | | 29 | | D40584P | | 51 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0036 | 20 | | GA | | 46-0 | 36-11-11 | D03538 | | 11 | | D40874P | | 31 | | 001-099 |
| 0036 | 20 | | GA | | 40-0 | 36-11-11 | D03538 | | 11 | | D40874P | | 31 | | 115-199 |
| 0037 | 20 | | GA | | 29-0 | 36-11-11 | D03538 | | 12 | | TB0058X | C010 | BJ | | ALL |
| 0038 | 24 | | GK | | 41-0 | 36-11-11 | D03538 | | 10 | | D40972P | | 18 | | 001-099 |
| 0038 | 24 | | GK | | 40-0 | 36-11-11 | D03538 | | 10 | | D40874P | | 30 | | 115-199 |
| 0039 | 22 | | GA | | 44-0 | 26-18-11 | D03538 | | 13 | | D40584P | | 21 | | ALL |
| 0040 | 24 | | GK | | 39-0 | 21-61-51 | D03556 | | 30 | | D41854P | | 10 | | 001-099 |
| 0040 | 24 | | GK | | 38-0 | 21-61-51 | D03556 | | 30 | | D41854P | | 10 | | 115-199 |
| 0041 | 22 | | GA | | 14-0 | 33-16-53 | D03708 | | 3 | | TB0116Z | | 9 | BJ | 001-003, 115-199 |
| 0042 | 16 | | GA | | 7-0 | 33-13-52 | D02890 | | 11 | 16 | GD02316 | AC.. | 2 | | ALL |
| 0043 | 22 | | GA | | 42-0 | 34-12-12 | D03702 | | 5 | | D40874P | | 24 | | 001-099 |
| 0043 | 22 | | GA | | 35-0 | 34-12-12 | D03702 | | 5 | | D40874P | | 24 | | 115-199 |
| 0044 | 22 | | GA | | 15-0 | 33-16-11 | SM00009 | | | 9 | D41170J | | 3 | | 001-099 |
| 0044 | 22 | | GA | | 11-0 | 33-16-11 | SM00009 | | | 9 | D41170J | | 3 | | 115-199 |
| 0050 | 22 | | GA | | 15-0 | 33-16-11 | TB0059X | B003 | BJ | | SM00023 | | 9 | | 115-199 |
| 0051 | 22 | | GA | | 15-0 | 33-16-11 | TB0059X | A003 | BJ | | SM00022 | | 9 | | 115-199 |
| 0055 | 22 | | GA | | 15-0 | 33-16-21 | SM00018 | | | 9 | D41170J | | 9 | | 001-099 |
| 0055 | 22 | | GA | | 11-0 | 33-16-21 | SM00018 | | | 9 | D41170J | | 9 | | 115-199 |
| 0056 | 22 | | GA | | 7-0 | 22-21-21 | D03702 | | 41 | | GD00620 | DC.. | 2 | | ALL |
| 0057 | 22 | | GA | | 7-0 | 30-41-11 | D03702 | | 7 | | GD00620 | DC.. | 2 | | ALL |
| 0058 | 22 | | GA | | 14-0 | 30-41-11 | D03702 | | 6 | | TB0112X | D016 | BJ | | 001-099 |
| 0058 | 22 | | GA | | 15-0 | 30-41-11 | D03702 | | 6 | | TB0112X | D016 | BJ | | 115-199 |
| 0059 | 24 | | GK | | 17-0 | 21-58-13 | D40584P | | 44 | | D40874P | | 6 | | 001-099 |
| 0059 | 24 | | GK | | 11-0 | 21-58-13 | D40584P | | 44 | | D40874P | | 6 | | 115-199 |
| 0060 | 24 | | GK | | 41-0 | 34-33-11 | D03702 | CAP | | Y | D41864P | | 24 | | ALL |
| 0061 | 24 | | GK | | 17-0 | 36-11-12 | D40584P | | 42 | | D40874P | | 33 | | 001-099 |
| 0061 | 24 | | GK | | 11-0 | 36-11-12 | D40874P | | 33 | | D40584P | | 42 | | 115-199 |
| 0063 | 24 | | GK | | 4-0 | 33-13-52 | D02894 | | 12 | | D07020 | | D2 | | ALL |
| 0064 | 20 | | GA | | 5-0 | 33-13-52 | D02894 | | 7 | | GD01649 | ST.. | 2 | *1 | ALL |
| 0065 | 20 | | GA | | 5-0 | 33-13-52 | D02894 | | 11 | | GD01649 | AC.. | 2 | | ALL |
| 0066 | 20 | | GA | | 5-0 | 33-13-52 | D02894 | | 2 | | TB0159Z | | 11 | BJ | ALL |
| 0067 | 16 | | GA | | 22-0 | 33-13-52 | TB0159F | A010 | | 2 | D02890 | | 8 | 16 | 001-099 |
| 0067 | 16 | | GA | | 23-0 | 33-13-52 | TB0159F | A010 | | 2 | D02890 | | 8 | 16 | 115-199 |
| 0068 | 20 | | GA | | 5-0 | 33-13-52 | D02890 | | 2 | | TB0101Z | | 9 | BJ | 001-099 |
| 0068 | 20 | | GA | | 8-0 | 33-13-52 | D02890 | | 2 | | TB0101Z | | 9 | BJ | 115-199 |
| 0069 | 20 | | GA | | 7-0 | 33-13-51 | D02892 | | 2 | | TB0100X | C002 | BJ | | 001-099 |
| 0069 | 20 | | GA | | 4-0 | 33-13-51 | D02892 | | 2 | | TB0100X | C002 | BJ | | 115-199 |
| 0070 | 22 | | GA | | 12-0 | 33-16-12 | TB0112Z | | 7 | BJ | D41000P | | 18 | | ALL |
| 0071 | 24 | | GK | | 44-0 | 21-31-11 | D02344 | | 31 | | D40584P | | 5 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0072 | 20 | | GA | | 1-0 | 33-13-31 | TB0114Z | 7 | BJ | | TB0114Z | 8 | BJ | | ALL |
| 0073 | 20 | | GA | | 6-0 | 33-13-31 | GD00603 | AC.. | 2 | | TB0114Z | 9 | BJ | | 001-099 |
| 0073 | 20 | | GA | | 5-0 | 33-13-31 | GD00603 | AC.. | 2 | | TB0114Z | 9 | BJ | | 115-199 |
| 0074 | 20 | | GA | | 6-0 | 33-13-31 | GD00603 | AC.. | 2 | | TB0114Z | 12 | BJ | | 001-099 |
| 0074 | 20 | | GA | | 5-0 | 33-13-31 | GD00603 | AC.. | 2 | | TB0114Z | 12 | BJ | | 115-199 |
| 0075 | 20 | | GA | | 7-0 | 33-13-31 | D03412 | | 7 | | GD00603 | ST.. | 2 | | ALL |
| 0076 | 20 | | GA | | 10-0 | 33-13-31 | D03412 | | 8 | | TB0116X | C018 | BJ | | ALL |
| 0077 | 20 | | GA | | 7-0 | 33-13-31 | D03412 | | 11 | | GD00603 | AC.. | 2 | | ALL |
| 0078 | 20 | | GA | | 7-0 | 33-13-31 | D03410 | | 11 | | GD00603 | AC.. | 2 | | 001-099 |
| 0078 | 20 | | GA | | 6-0 | 33-13-31 | D03410 | | 11 | | GD00603 | AC.. | 2 | | 115-199 |
| 0079 | 20 | | GA | | 8-0 | 33-13-31 | D03410 | | 2 | | TB0114Z | 7 | BJ | | ALL |
| 0080 | 20 | | GA | | 7-0 | 33-13-31 | D03410 | | 7 | | GD00603 | ST.. | 2 | | 001-099 |
| 0080 | 20 | | GA | | 6-0 | 33-13-31 | D03410 | | 7 | | GD00603 | ST.. | 2 | | 115-199 |
| 0081 | 24 | | GK | | 44-0 | 36-11-12 | D03538 | | 5 | | D40584P | 36 | | | ALL |
| 0082 | 20 | | GA | | 2-0 | 33-13-31 | TB0114Z | | 9 | BJ | TB0114Z | 10 | BJ | | ALL |
| 0083 | 24 | | GK | | 17-0 | 24-11-11 | D41864P | | 26 | | D40584P | 26 | | | ALL |
| 0084 | 24 | | GK | | 17-0 | 24-11-11 | D41864P | | 27 | | D40584P | 25 | | | ALL |
| 0085 | 24 | | GK | | 17-0 | 24-11-11 | D41864P | | 28 | | D40584P | 24 | | | ALL |
| 0086 | 24 | | GK | | 17-0 | 24-11-11 | D41864P | | 29 | | D40584P | 23 | | | ALL |
| 0087 | 22 | | GA | | 41-0 | 27-28-13 | D01876 | | 3 | | D40584P | 4 | | | ALL |
| 0088 | 22 | | GA | | 44-0 | 28-42-11 | D03512 | | 8 | | D40584P | 40 | | | ALL |
| 0089 | 22 | | GA | | 44-0 | 28-42-11 | D03512 | | 11 | | D40584P | 29 | | | ALL |
| 0090 | 22 | | GA | | 12-4 | 28-42-11 | D03512 | | 10 | | SM00055 | | 9 | | ALL |
| 0091 | 22 | | GA | | 44-0 | 28-42-11 | D03512 | | 5 | | D40584P | 20 | | | ALL |
| 0092 | 24 | | GK | | 7-0 | 21-65-11 | D40800J | | 32 | | D03578 | 3 | | | ALL |
| 0094 | 22 | | GA | | 36-0 | SPARE | D03702 | CAP | Y | | D40972P | 2 | | | 001-099 |
| 0094 | 22 | | GA | | 35-0 | SPARE | D03702 | CAP | Y | | D40972P | 2 | | | 115-199 |
| 0096 | 22 | | GA | | 45-0 | 29-32-21 | D03544 | | 13 | | D40584P | 1 | | | ALL |
| 0097 | 22 | | GA | | 45-0 | 29-32-21 | D03544 | | 15 | | D40584P | 2 | | | ALL |
| 0099 | 20 | | GA | | 43-0 | 36-11-11 | D40874P | | 29 | | TB0058X | D010 | BJ | | 001-099 |
| 0099 | 20 | | GA | | 37-0 | 36-11-11 | D40874P | | 29 | | TB0058X | D010 | BJ | | 115-199 |
| 0102 | 24 | | GK | | 41-0 | 21-61-11 | D40800J | | 33 | | D41854P | 30 | | | 001-099 |
| 0102 | 24 | | GK | | 39-0 | 21-61-11 | D40800J | | 33 | | D41854P | 30 | | | 115-199 |
| 0103 | 20 | | GA | | 7-0 | 21-61-51 | D40800J | | 34 | | D03556 | 24 | | | ALL |
| 0104 | 24 | | GK | | 41-0 | SPARE | D40800J | | 35 | | D41854P | 8 | | | 001-099 |
| 0104 | 24 | | GK | | 39-0 | SPARE | D40800J | | 35 | | D41854P | 8 | | | 115-199 |
| 0105 | 20 | | GA | | 4-0 | 21-51-11 | D03556 | | 6 | | GD00605 | DC.. | 2 | | 001-099 |
| 0105 | 20 | | GA | | 5-0 | 21-51-11 | D03556 | | 6 | | GD00605 | DC.. | 2 | | 115-199 |
| 0106 | 16 | | GA | | 14-0 | 29-11-22 | D40800J | | 36 | 16 | SM00021 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|------|--|---------|-------|------|------|---------|-------|------|------|---------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2066 | 286N2066 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | | |
| 0106 | 16 | GA | | 4-0 | 29-11-22 | D40800J | 36 | 16 | | SM00021 | | 9 | | 115-199 | | | |
| 0107 | 24 | GK | | 7-0 | 24-11-11 | D03708 | 6 | | | GD00620 | DC.. | 2 | | ALL | | | |
| 0108 | 20 | GA | | 42-0 | 24-22-11 | D03500 | 22 | | | D40580P | 24 | | | 001-099 | | | |
| 0108 | 20 | GA | | 41-0 | 24-22-11 | D03500 | 22 | | | D40580P | 24 | | | 115-199 | | | |
| 0109 | 20 | GA | | 42-0 | 24-22-12 | D03500 | 30 | | | D40580P | 9 | | | 001-099 | | | |
| 0109 | 20 | GA | | 41-0 | 24-22-12 | D03500 | 30 | | | D40580P | 9 | | | 115-199 | | | |
| 0110 | 22 | GA | | 47-0 | 24-22-12 | D03500 | 31 | | | D41864P | 1 | | | 001-099 | | | |
| 0110 | 22 | GA | | 46-0 | 24-22-12 | D03500 | 31 | | | D41864P | 1 | | | 115-199 | | | |
| 0111 | 24 | GK | | 42-0 | 24-27-11 | D03500 | 28 | | | D40580P | 26 | | | 001-099 | | | |
| 0111 | 24 | GK | | 41-0 | 24-27-11 | D03500 | 28 | | | D40580P | 26 | | | 115-199 | | | |
| 0112 | 22 | GA | | 7-0 | 24-34-11 | D03500 | 14 | | | TB0115X | C004 | BJ | | ALL | | | |
| 0113 | 22 | GA | | 7-0 | 24-34-11 | D03500 | 32 | | | TB0115X | D004 | BJ | | ALL | | | |
| 0114 | 20 | GA | | 5-0 | 24-51-14 | D03500 | 10 | | | D40800J | 10 | | | 001-099 | | | |
| 0114 | 20 | GA | | 6-0 | 24-51-14 | D03500 | 10 | | | D40800J | 10 | | | 115-199 | | | |
| 0115 | 20 | GA | | 47-0 | 24-51-14 | D03500 | 8 | | | D42074P | 1 | | | ALL | | | |
| 0116 | 20 | GA | | 47-0 | 24-51-14 | D03500 | 5 | | | D42074P | 2 | | | ALL | | | |
| 0117 | 24 | GK | | 41-0 | 24-51-71 | D03544 | 28 | | | D41854P | 19 | | | 001-099 | | | |
| 0117 | 22 | GA | | 39-0 | 24-51-71 | D03544 | 28 | | | D41854P | 19 | | | 115-199 | | | |
| 0118 | 24 | GK | | 48-0 | 24-51-71 | D40800J | 38 | | | D40874P | 15 | | | 001-099 | | | |
| 0118 | 22 | GA | | 42-0 | 24-51-71 | D40800J | 38 | | | D40874P | 15 | | | 115-199 | | | |
| 0120 | 24 | GK | | 48-0 | 24-51-71 | D40874P | 16 | | | D03544 | 27 | | | 001-099 | | | |
| 0120 | 22 | GA | | 42-0 | 24-51-71 | D40874P | 16 | | | D03544 | 27 | | | 115-199 | | | |
| 0122 | 24 | GK | | 42-0 | 24-51-71 | D03500 | 6 | | | D40580P | 12 | | | 001-099 | | | |
| 0122 | 24 | GK | | 41-0 | 24-51-71 | D03500 | 6 | | | D40580P | 12 | | | 115-199 | | | |
| 0123 | 24 | GK | | 9-0 | 24-51-71 | D03500 | 24 | | | TB0116X | A018 | BJ | | ALL | | | |
| 0124 | 22 | GA | | 5-0 | 24-51-24 | D03500 | 12 | | | GD00601 | DC.. | 2 | | 001-099 | | | |
| 0124 | 22 | GA | | 4-0 | 24-51-24 | D03500 | 12 | | | GD00601 | DC.. | 2 | | 115-199 | | | |
| 0125 | 24 | GK | | 40-0 | 24-51-71 | D03500 | 35 | | | D41854P | 1 | | | 001-099 | | | |
| 0125 | 22 | GA | | 39-0 | 24-51-71 | D03500 | 35 | | | D41854P | 1 | | | 115-199 | | | |
| 0126 | 22 | GA | | 5-0 | 24-51-24 | D03500 | 37 | | | TB0113X | C015 | BJ | | ALL | | | |
| 0127 | 22 | GA | | 5-0 | 24-51-14 | D03500 | 9 | | | TB0113X | D015 | BJ | | ALL | | | |
| 0129 | 24 | GK | | 11-0 | SPARE | D40972P | 12 | | | D41854P | 9 | | | 001-099 | | | |
| 0129 | 24 | GK | | 10-0 | SPARE | D40972P | 12 | | | D41854P | 9 | | | 115-199 | | | |
| 0130 | 24 | GK | | 22-0 | SPARE | D40584P | CAP | Y | | D41854P | 3 | | | 001-099 | | | |
| 0130 | 24 | GK | | 20-0 | SPARE | D40584P | CAP | Y | | D41854P | 3 | | | 115-199 | | | |
| 0131 | 24 | GK | | 17-0 | SPARE | D41864P | 4 | | | D40584P | 38 | | | 001-099 | | | |
| 0136 | 24 | GK | | 39-0 | 36-11-31 | D03538 | 8 | | | D41854P | 4 | | | 001-099 | | | |
| 0136 | 24 | GK | | 38-0 | 36-11-31 | D03538 | 8 | | | D41854P | 4 | | | 115-199 | | | |
| 0137 | 24 | GK | | 39-0 | 36-11-31 | D03538 | 9 | | | D41854P | 5 | | | 001-099 | | | |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 9

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|--|----------|---------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | | |
| 0191 | 22 | GA | | 18-0 | 33-51-11 | | D40456P | | 3 | | | TB0113X | A015 | BJ | | 001-099 |
| 0191 | 22 | GA | | 19-0 | 33-51-11 | | D40456P | | 3 | | | TB0113X | A015 | BJ | | 115-199 |
| 0195 | 24 | GK | | 46-0 | 21-25-11 | | D03556 | | 13 | | | D42074P | 3 | | | 001-099 |
| 0195 | 24 | GK | | 45-0 | 21-25-11 | | D03556 | | 13 | | | D42074P | 3 | | | 115-199 |
| 0197 | 22 | GA | | 14-0 | 33-16-11 | | D40800J | | 3 | | | D41000P | 10 | | | 001-099 |
| 0197 | 22 | GA | | 15-0 | 33-16-11 | | D40800J | | 3 | | | D41000P | 10 | | | 115-199 |
| 0198 | 22 | GA | | 14-0 | 33-16-11 | | D40800J | | 4 | | | SM00011 | | 9 | | 001-099 |
| 0198 | 22 | GA | | 18-0 | 33-16-11 | | D40800J | | 4 | | | SM00011 | | 9 | | 115-199 |
| 0199 | 22 | GA | | 17-0 | 33-16-11 | | D41834J | | 4 | | | D41000P | 21 | | | 001-099 |
| 0199 | 22 | GA | | 16-0 | 33-16-11 | | D41834J | | 4 | | | D41000P | 21 | | | 115-199 |
| 0200 | 22 | GA | | 15-0 | 33-16-11 | | D41834J | | 5 | | | SM00009 | | 9 | | 001-099 |
| 0200 | 22 | GA | | 11-0 | 33-16-11 | | D41834J | | 5 | | | SM00009 | | 9 | | 115-199 |
| 0201 | 22 | GA | | 15-0 | 33-16-11 | | D41834J | | 7 | | | SM00009 | | 9 | | 001-099 |
| 0201 | 22 | GA | | 11-0 | 33-16-11 | | D41834J | | 7 | | | SM00009 | | 9 | | 115-199 |
| 0202 | 22 | GA | | 15-0 | 33-16-11 | | D41834J | | 8 | | | SM00011 | | 9 | | 001-099 |
| 0202 | 22 | GA | | 11-0 | 33-16-11 | | D41834J | | 8 | | | SM00011 | | 9 | | 115-199 |
| 0203 | 22 | GA | | 17-0 | 33-16-11 | | D41834J | | 9 | | | D41000P | 20 | | | 001-099 |
| 0203 | 22 | GA | | 16-0 | 33-16-11 | | D41834J | | 9 | | | D41000P | 20 | | | 115-199 |
| 0204 | 22 | GA | | 4-0 | 33-16-11 | | D41000P | | 1 | | | SM00011 | | 9 | | 001-099 |
| 0204 | 22 | GA | | 7-0 | 33-16-11 | | D41000P | | 1 | | | SM00011 | | 9 | | 115-199 |
| 0205 | 22 | GA | | 12-0 | 33-16-12 | | SM00009 | | 9 | | | TB0112Z | 11 | BJ | | 001-099 |
| 0205 | 22 | GA | | 15-0 | 33-16-12 | | SM00009 | | 9 | | | TB0112Z | 11 | BJ | | 115-199 |
| 0206 | 22 | GA | | 4-0 | 33-16-11 | | D41000P | | 2 | | | SM00009 | | 9 | | 001-099 |
| 0206 | 22 | GA | | 7-0 | 33-16-11 | | D41000P | | 2 | | | SM00009 | | 9 | | 115-199 |
| 0207 | 20 | GA | | 4-0 | 33-16-11 | | D41000P | | 17 | | | GD01220 | DC.. | 2 | | ALL |
| 0208 | 20 | GA | | 4-0 | 33-16-11 | | D41000P | | 15 | | | GD01220 | DC.. | 2 | | ALL |
| 0209 | 20 | GA | | 4-0 | 33-16-11 | | D41000P | | 6 | | | GD01220 | DC.. | 2 | | ALL |
| 0210 | 20 | GA | | 4-0 | 33-16-11 | | D41000P | | 5 | | | GD01220 | DC.. | 2 | | ALL |
| 0211 | 20 | GA | | 4-0 | 33-16-11 | | D41000P | | 14 | | | GD01220 | DC.. | 2 | | ALL |
| 0212 | 22 | GA | | 5-0 | 33-16-13 | | D41000P | | 16 | | | TB0121Z | 15 | BJ | | 001-099 |
| 0212 | 22 | GA | | 8-0 | 33-16-13 | | SM00023 | | 9 | | | TB0121Z | 15 | BJ | | 115-199 |
| 0213 | 22 | GA | | 5-0 | 33-16-13 | | D41000P | | 12 | | | TB0121Z | 10 | BJ | | 001-099 |
| 0213 | 22 | GA | | 8-0 | 33-16-13 | | SM00022 | | 9 | | | TB0121Z | 10 | BJ | | 115-199 |
| 0214 | 22 | GA | | 38-0 | 33-16-11 | | D41000P | | 3 | | | D40874P | 11 | | | 001-099 |
| 0214 | 22 | GA | | 32-0 | 33-16-11 | | D41000P | | 3 | | | D40874P | 11 | | | 115-199 |
| 0215 | 24 | GK | | 17-0 | 21-58-21 | | D40584P | | 8 | | | D40874P | 9 | | | 001-099 |
| 0215 | 24 | GK | | 11-0 | 21-58-21 | | D40584P | | 8 | | | D40874P | 9 | | | 115-199 |
| 0216 | 20 | GA | | 5-0 | 28-41-11 | | D06872 | | 9 | | | GD00603 | ST.. | 2 | | 001-099 |
| 0216 | 20 | GA | | 5-0 | 28-41-11 | | D06872 | | 9 | | | GD00605 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|--------|---------|------|-------------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | | |
| 0217 | 24 | | GK | | 32-0 | 34-22-16 | D40800J | 51 | | | | TB0101X | C001 | BJ | | 001-099 |
| 0217 | 24 | | GK | | 33-0 | 34-22-16 | D40800J | 51 | | | | TB0101X | C001 | BJ | | 115-199 |
| 0218 | 20 | | GA | | 7-0 | 33-42-21 | D40800J | 7 | | | | TB0115X | B002 | BJ | | ALL |
| 0219 | 20 | | GA | | 5-0 | 33-42-31 | D40800J | 37 | | | | TB0113Y | C005 | BJ | | 001-099 |
| 0220 | 24 | | GK | | 40-0 | 21-51-11 | D03556 | 2 | | | | D40972P | 5 | | | ALL |
| 0221 | 24 | | GK | | 8-0 | 21-51-12 | TB0115X | B16 | BJ | | | D03556 | 5 | | | 001-099 |
| 0221 | 24 | | GK | | 8-0 | 21-51-12 | TB0115X | B016 | BJ | | | D03556 | 5 | | | 115-199 |
| 0222 | 24 | | GK | | 46-0 | 21-51-12 | D03556 | 1 | | | | D40874P | 17 | | | 001-099 |
| 0222 | 24 | | GK | | 40-0 | 21-51-12 | D03556 | 1 | | | | D40874P | 17 | | | 115-199 |
| 0223 | 24 | | GK | | 40-0 | 21-51-15 | D03556 | 18 | | | | D40972P | 6 | | | ALL |
| 0224 | 24 | | GK | | 4-0 | 21-51-15 | D03556 | 19 | | | | GD00605 | DC.. | 2 | | 001-099 |
| 0224 | 24 | | GK | | 5-0 | 21-51-15 | D03556 | 19 | | | | GD00605 | DC.. | 2 | | 115-199 |
| 0225 | 24 | | GK | | 40-0 | 21-51-15 | D03556 | 20 | | | | D40972P | 7 | | | ALL |
| 0226 | 24 | | GK | | 40-0 | 21-51-15 | D03556 | 21 | | | | D40972P | 8 | | | ALL |
| 0227 | 24 | | GK | | 23-0 | 21-51-15 | D40972P | 9 | | | | D40584P | 9 | | | 001-099 |
| 0227 | 24 | | GK | | 22-0 | 21-51-15 | D40972P | 9 | | | | D40584P | 9 | | | 115-199 |
| 0228 | 24 | | GK | | 23-0 | 21-51-15 | D40972P | 10 | | | | D40584P | 10 | | | 001-099 |
| 0228 | 24 | | GK | | 22-0 | 21-51-15 | D40972P | 10 | | | | D40584P | 10 | | | 115-199 |
| 0229 | 20 | | GA | | 4-0 | 21-51-23 | D03556 | 12 | | | | GD00605 | DC.. | 2 | | 001-099 |
| 0229 | 20 | | GA | | 5-0 | 21-51-23 | D03556 | 12 | | | | GD00605 | DC.. | 2 | | 115-199 |
| 0230 | 24 | | GK | | 40-0 | 21-51-23 | D03556 | 11 | | | | D40972P | 1 | | | ALL |
| 0231 | 24 | | GK | | 40-0 | 21-51-23 | D03556 | 9 | | | | D40972P | 13 | | | ALL |
| 0232 | 24 | | GK | | 40-0 | 21-51-23 | D03556 | 8 | | | | D40972P | 3 | | | ALL |
| 0233 | 24 | | GK | | 40-0 | 21-51-23 | D03556 | 7 | | | | D40972P | 4 | | | ALL |
| 0234 | 24 | | GK | | 17-0 | 21-58-12 | D40584P | 48 | | | | D40874P | 42 | | | 001-099 |
| 0234 | 24 | | GK | | 11-0 | 21-58-12 | D40584P | 48 | | | | D40874P | 42 | | | 115-199 |
| 0235 | 24 | | GK | | 17-0 | 21-58-11 | D40584P | 49 | | | | D40874P | 34 | | | 001-099 |
| 0235 | 24 | | GK | | 11-0 | 21-58-11 | D40584P | 49 | | | | D40874P | 34 | | | 115-199 |
| 0236 | 24 | | GK | | 17-0 | 21-58-11 | D40584P | 50 | | | | D40874P | 35 | | | 001-099 |
| 0236 | 24 | | GK | | 11-0 | 21-58-11 | D40584P | 50 | | | | D40874P | 35 | | | 115-199 |
| 0237 | 24 | | GK | | 41-0 | 27-32-21 | D03702 | 8 | | | | D41864P | 5 | | | ALL |
| 0238 | 24 | | GK | | 24-0 | SPARE | D41854P | 2 | | | | D41864P | 37 | | | 001-099 |
| 0239 | 24 | | GK | | 17-0 | 21-58-11 | D40874P | 10 | | | | D40584P | 35 | | | 001-099 |
| 0239 | 24 | | GK | | 11-0 | 21-58-11 | D40874P | 10 | | | | D40584P | 35 | | | 115-199 |
| 0240 | 24 | | GK | | 17-0 | SPARE | D40874P | 18 | | | | D40584P | 12 | | | 001-099 |
| 0240 | 24 | | GK | | 11-0 | SPARE | D40874P | 18 | | | | D40584P | 12 | | | 115-199 |
| 0241 | 24 | | GK | | 7-0 | SPARE | D03538 | 14 | | | | D40800J | 55 | | | 001-099 |
| 0241 | 24 | | GK | | 8-0 | SPARE | D03538 | 14 | | | | D40800J | 55 | | | 115-199 |
| 0244 | 24 | | GK | | 4-0 | 21-61-51 | D03556 | 28 | | | | GD00605 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2066 | 286N2066 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | | |
| 0244 | 24 | | GK | | 5-0 | 21-61-51 | D03556 | | | 28 | | GD00605 | DC.. | 2 | | 115-199 | |
| 0245 | 20 | | GA | | 46-0 | 21-61-51 | D03556 | | | 35 | | D40874P | 8 | | | 001-099 | |
| 0245 | 20 | | GA | | 40-0 | 21-61-51 | D03556 | | | 35 | | D40874P | 8 | | | 115-199 | |
| 0246 | 24 | | GK | | 38-0 | SPARE | D03556 | | | 34 | | D41854P | 31 | | | 115-199 | |
| 0247 | 24 | | GK | | 4-0 | 21-61-51 | D03556 | | | 25 | | GD00605 | DC.. | 2 | | 001-099 | |
| 0247 | 24 | | GK | | 5-0 | 21-61-51 | D03556 | | | 25 | | GD00605 | DC.. | 2 | | 115-199 | |
| 0248 | 24 | | GK | | 43-0 | 21-61-51 | D03556 | | | 27 | | D40584P | 11 | | | ALL | |
| 0251 | 24 | | GK | | 4-0 | 21-65-11 | D03578 | | | 11 | | GD00605 | ST.. | 2 | | 001-099 | |
| 0251 | 24 | | GK | | 5-0 | 21-65-11 | D03578 | | | 11 | | GD00605 | ST.. | 2 | | 115-199 | |
| 0252 | 24 | | GK | | 4-0 | 21-65-11 | D03578 | | | 4 | | GD00605 | DC.. | 2 | | 001-099 | |
| 0252 | 24 | | GK | | 5-0 | 21-65-11 | D03578 | | | 4 | | GD00605 | DC.. | 2 | | 115-199 | |
| 0253 | 22 | | GA | | 17-0 | 27-23-11 | D40800J | | | 28 | | D03708 | 12 | | | ALL | |
| 0254 | 22 | | GA | | 42-0 | 27-23-11 | D40874P | | | 13 | | D03708 | 11 | | | 001-099 | |
| 0254 | 22 | | GA | | 35-0 | 27-23-11 | D40874P | | | 13 | | D03708 | 11 | | | 115-199 | |
| 0255 | 22 | | GA | | 42-0 | 27-23-11 | D40874P | | | 14 | | D03708 | 10 | | | 001-099 | |
| 0255 | 22 | | GA | | 35-0 | 27-23-11 | D40874P | | | 14 | | D03708 | 10 | | | 115-199 | |
| 0256 | 22 | | GA | | 18-0 | 33-51-11 | D40456P | | | 4 | | TB0113Z | 14 | BJ | | 001-099 | |
| 0256 | 22 | | GA | | 19-0 | 33-51-11 | D40456P | | | 4 | | TB0113Z | 14 | BJ | | 115-199 | |
| 0257 | 22 | | GA | | 18-0 | 33-51-11 | D40454P | | | 3 | | TB0113Z | 13 | BJ | | 001-099 | |
| 0257 | 22 | | GA | | 19-0 | 33-51-11 | D40454P | | | 3 | | TB0113Z | 13 | BJ | | 115-199 | |
| 0258 | 22 | | GA | | 18-0 | 33-51-11 | D40454P | | | 4 | | TB0113Z | 14 | BJ | | 001-099 | |
| 0258 | 22 | | GA | | 19-0 | 33-51-11 | D40454P | | | 4 | | TB0113Z | 14 | BJ | | 115-199 | |
| 0260 | 20 | | GA | | 30-0 | 27-62-11 | D40800J | | | 22 | | TB0100X | A004 | BJ | | 001-099 | |
| 0260 | 22 | | GA | | 29-0 | 27-62-11 | D40800J | | | 22 | | TB0100X | A004 | BJ | | 115-199 | |
| 0262 | 20 | | GA | | 6-0 | 27-21-11 | D01744 | | | 11 | | TB0158X | D003 | BJ | | 001-099 | |
| 0263 | 20 | | GA | | 6-0 | 27-21-11 | D01744 | | | 6 | | TB0158X | B003 | BJ | | 001-099 | |
| 0264 | 20 | | GA | | 5-0 | 33-13-52 | D02894 | | | 9 | | TB0159Z | 12 | BJ | | ALL | |
| 0266 | 20 | | GA | | 29-0 | 28-22-11 | D03512 | | | 15 | | D41870P | 14 | | | ALL | |
| 0267 | 20 | | GA | | 6-0 | 27-21-11 | D01744 | | | 14 | | TB0158X | C003 | BJ | | 001-099 | |
| 0268 | 18 | | GA | | 25-0 | SPARE | D41870P | | | 3 | 18 | D40972P | 14 | 18 | | 001-099 | |
| 0268 | 18 | | GA | | 22-0 | SPARE | D41870P | | | 3 | 18 | D40972P | 14 | 18 | | 115-199 | |
| 0269 | 20 | | GA | | 22-0 | SPARE | D41870P | | | 2 | | D40972P | 15 | | | ALL | |
| 0270 | 24 | | GK | | 51-0 | SPARE | D03510 | | | 38 | | D40996P | 8 | | | 115-199 | |
| 0271 | 24 | | GK | | 23-0 | 36-11-11 | D40584P | | | 27 | | D40972P | 19 | | | 001-099 | |
| 0273 | 24 | | GK | | 25-0 | SPARE | D40972P | | | 28 | | D42074P | 11 | | | 001-099 | |
| 0273 | 24 | | GK | | 24-0 | SPARE | D40972P | | | 28 | | D42074P | 11 | | | 115-199 | |
| 0274 | 24 | | GK | | 17-0 | 21-58-12 | D40584P | | | 52 | | D40874P | 40 | | | 001-099 | |
| 0274 | 24 | | GK | | 11-0 | 21-58-12 | D40874P | | | 40 | | D40584P | 52 | | | 115-199 | |
| 0276 | 24 | | GK | | 7-0 | 24-51-31 | D40800J | | | 45 | | TB0111A | A003 | 2 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|---------|-------|------|-------------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0277 | 24 | GK | | | 51-0 | SPARE | D03510 | 25 | | | D40996P | 15 | | | 115-199 |
| 0279 | 22 | GA | | | 18-6 | 28-22-11 | D41870P | 9 | | | SM00055 | | 9 | | ALL |
| 0280 | 24 | GK | | | 24-0 | 21-58-12 | D42074P | 8 | | | D41854P | 7 | | | 001-099 |
| 0280 | 24 | GK | | | 22-0 | 21-58-12 | D42074P | 8 | | | D41854P | 7 | | | 115-199 |
| 0283 | 24 | GK | | | 41-0 | 21-58-21 | D40800J | 20 | | | D41854P | 16 | | | 001-099 |
| 0283 | 24 | GK | | | 39-0 | 21-58-21 | D40800J | 20 | | | D41854P | 16 | | | 115-199 |
| 0284 | 22 | GA | | | 7-0 | 33-16-11 | D41000P | 16 | | | SM00023 | | 9 | | 115-199 |
| 0285 | 24 | GK | | | 24-0 | 21-25-11 | D42074P | 10 | | | D41854P | 21 | | | 001-099 |
| 0285 | 24 | GK | | | 22-0 | 21-25-11 | D42074P | 10 | | | D41854P | 21 | | | 115-199 |
| 0286 | 24 | GK | | | 11-0 | 21-51-11 | D41854P | 6 | | | D40972P | 29 | | | 001-099 |
| 0287 | 20 | GA | | | 41-0 | 21-51-23 | D40800J | 39 | | | D41854P | 22 | | | 001-099 |
| 0288 | 18 | GA | | | 7-0 | 28-43-11 | D40800J | 23 | 18 | | D03584 | 9 | 18 | | 115-199 |
| 0289 | 20 | GA | | | 5-0 | 28-43-11 | D06872 | 10 | | | GD00603 | ST.. | 2 | | 001-099 |
| 0289 | 22 | GA | | | 17-0 | 28-43-11 | D03702 | 35 | | | D03584 | 11 | | | 115-199 |
| 0290 | 22 | GA | | | 16-0 | 28-43-11 | D03702 | 36 | | | GD00603 | DC.. | 2 | | 115-199 |
| 0291 | 22 | GA | | | 32-9 | 28-42-11 | D40584P | 19 | | | SM00055 | | 9 | | ALL |
| 0293 | 18 | GA | | | 4-0 | 28-43-11 | D06872 | 10 | 18 | | GD00601 | ST.. | 2 | | 115-199 |
| 0294 | 20 | GA | | | 29-0 | 28-22-11 | D03512 | 27 | | | D41870P | 27 | | | ALL |
| 0295 | 20 | GA | | | 29-0 | 28-22-11 | D03512 | 13 | | | D41870P | 15 | | | ALL |
| 0297 | 18 | GA | | | 5-0 | 25-31-33 | D40800J | 21 | 18 | | D03500 | 34 | 18 | | 001-099 |
| 0297 | 18 | GA | | | 6-0 | 25-31-33 | D40800J | 21 | 18 | | D03500 | 34 | 18 | | 115-199 |
| 0299 | 22 | GA | | | 12-0 | 33-16-12 | D41000P | 13 | | | TB0112X | A016 | BJ | | ALL |
| 0300 | 22 | GA | | | 12-0 | 33-16-12 | D41000P | 19 | | | TB0112Y | A002 | BJ | | ALL |
| 0301 | 24 | GK | | | 14-0 | 33-16-12 | D41000P | 4 | | | TB0113Y | C006 | BJ | | 001-099 |
| 0301 | 24 | GK | | | 14-0 | 33-16-12 | D41000P | 4 | | | SP01936 | | 9 | | 115-199 |
| 0302 | 22 | GA | | | 6-0 | 33-16-13 | D03708 | 4 | | | TB0121Z | 10 | BJ | | 001-099 |
| 0302 | 22 | GA | | | 5-0 | 33-16-13 | D03708 | 4 | | | TB0121Z | 10 | BJ | | 115-199 |
| 0305 | 22 | GA | | | 7-0 | 33-16-12 | D03538 | 3 | | | TB0112Z | 6 | BJ | | ALL |
| 0306 | 22 | GA | | | 7-0 | 33-16-12 | D03538 | 4 | | | TB0112Z | 7 | BJ | | ALL |
| 0307 | 22 | GA | | | 7-0 | 33-16-12 | D03556 | 3 | | | TB0112Z | 6 | BJ | | ALL |
| 0308 | 22 | GA | | | 7-0 | 33-16-12 | D03556 | 4 | | | TB0112Z | 8 | BJ | | ALL |
| 0309 | 22 | GA | | | 8-0 | 33-16-12 | D03512 | 4 | | | TB0112Z | 11 | BJ | | ALL |
| 0310 | 22 | GA | | | 8-0 | 33-16-12 | D03512 | 3 | | | TB0112Z | 6 | BJ | | ALL |
| 0311 | 22 | GA | | | 8-0 | 33-16-12 | D03500 | 27 | | | TB0112Z | 5 | BJ | | ALL |
| 0312 | 22 | GA | | | 8-0 | 33-16-12 | D03500 | 11 | | | TB0112Z | 8 | BJ | | ALL |
| 0313 | 22 | GA | | | 9-0 | 33-16-12 | D03544 | 3 | | | TB0112Z | 5 | BJ | | ALL |
| 0314 | 22 | GA | | | 9-0 | 33-16-12 | D03544 | 4 | | | TB0112Z | 8 | BJ | | ALL |
| 0315 | 20 | PA | | | 33-0 | 28-22-11 | D03512 | 17 | | | D41870P | 31 | | | ALL |
| 0316 | 20 | PA | | | 1-0 | 28-22-11 | D03512 | 18 | | | SM00009 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0317 | 18 | | PA | 1-0 | 28-22-11 | D03512 | | 19 | | SM00009 | | 9 | | ALL | |
| 0322 | 22 | | GA | 14-0 | 33-16-21 | D40800J | | 17 | | D41002P | | 1 | | 001-099 | |
| 0322 | 22 | | GA | 15-0 | 33-16-21 | D40800J | | 17 | | D41002P | | 1 | | 115-199 | |
| 0323 | 22 | | GA | 7-0 | 33-16-21 | D41002P | | 9 | | SM00017 | | 9 | | 115-199 | |
| 0324 | 22 | | GA | 12-0 | 33-16-21 | D41002P | | 8 | | TB0112X | B016 | BJ | | ALL | |
| 0325 | 22 | | GA | 4-0 | 33-16-21 | D41002P | | 2 | | SM00018 | | 9 | | 001-099 | |
| 0325 | 22 | | GA | 7-0 | 33-16-21 | D41002P | | 2 | | SM00018 | | 9 | | 115-199 | |
| 0326 | 22 | | GA | 15-0 | 33-16-21 | D41834J | | 10 | | SM00018 | | 9 | | 001-099 | |
| 0326 | 22 | | GA | 11-0 | 33-16-21 | D41834J | | 10 | | SM00018 | | 9 | | 115-199 | |
| 0327 | 22 | | GA | 16-0 | 33-16-21 | D41834J | | 12 | | D41002P | | 6 | | ALL | |
| 0328 | 16 | | GA | 4-0 | 33-16-21 | D41002P | | 4 | | GD01220 | DC.. | 2 | | ALL | |
| 0329 | 22 | | GA | 11-0 | SPARE | D41834J | | 11 | | SM00017 | | 9 | | 115-199 | |
| 0330 | 22 | | GA | 15-0 | 33-16-21 | D41834J | | 13 | | SM00019 | | 9 | | 001-099 | |
| 0330 | 22 | | GA | 11-0 | 33-16-21 | D41834J | | 13 | | SM00019 | | 9 | | 115-199 | |
| 0331 | 22 | | GA | 4-0 | 33-16-21 | D41002P | | 3 | | SM00019 | | 9 | | 001-099 | |
| 0331 | 22 | | GA | 7-0 | 33-16-21 | D41002P | | 3 | | SM00019 | | 9 | | 115-199 | |
| 0332 | 22 | | GA | 8-0 | 33-16-62 | D02344 | | 3 | | TB0116Z | | 4 | BJ | ALL | |
| 0333 | 22 | | GA | 8-0 | 33-16-52 | D02344 | | 4 | | TB0116Z | | 3 | BJ | ALL | |
| 0334 | 22 | | GA | 9-0 | 33-16-52 | D03500 | | 3 | | TB0116Z | | 9 | BJ | ALL | |
| 0335 | 22 | | GA | 9-0 | 33-16-52 | D03500 | | 4 | | TB0116Z | | 14 | BJ | ALL | |
| 0336 | 24 | | GK | 44-0 | 34-46-11 | D03702 | | 2 | | D40996P | | 11 | | 001-099 | |
| 0336 | 24 | | GK | 45-0 | 34-46-11 | D03702 | | 2 | | D40996P | | 11 | | 115-199 | |
| 0337 | 22 | | GA | 7-0 | 34-46-11 | D03702 | | 3 | | GD00620 | DC.. | 2 | | ALL | |
| 0338 | 24 | | GK | 16-0 | 22-21-21 | D03702 | | 40 | | TB0113X | A001 | BJ | | 001-099 | |
| 0338 | 24 | | GK | 17-0 | 22-21-21 | D03702 | | 40 | | TB0113X | A001 | BJ | | 115-199 | |
| 0339 | 22 | | GA | 7-0 | 27-32-21 | D03702 | | 9 | | GD00620 | DC.. | 2 | | ALL | |
| 0340 | 22 | | GA | 18-0 | 34-22-81 | D41170J | | 11 | | TB0121X | A019 | BJ | | 001-099 | |
| 0340 | 22 | | GA | 17-0 | 34-22-83 | D41170J | | 11 | | TB0121X | A019 | BJ | | 115-199 | |
| 0341 | 24 | | GK | 32-0 | 34-61-11 | D40800J | | 27 | | TB0101X | D002 | BJ | | 001-099 | |
| 0341 | 24 | | GK | 33-0 | 34-61-11 | D40800J | | 27 | | TB0101X | D002 | BJ | | 115-199 | |
| 0342 | 24 | | GK | 7-0 | 33-13-31 | D40800J | | 6 | | TB0111Y | C006 | BJ | | ALL | |
| 0343 | 24 | | GK | 3-0 | 33-13-31 | D04836 | | D2 | | D03412 | | 12 | | ALL | |
| 0344 | 22 | | GA | 15-0 | 29-11-22 | SM00021 | | | 9 | TB0111B | C017 | 2 | | 001-099 | |
| 0344 | 22 | | GA | 5-0 | 29-11-22 | SM00021 | | | 9 | TB0111B | C017 | 2 | | 115-199 | |
| 0345 | 22 | | GA | 1-0 | 29-11-22 | TB0111B | | A017 | 2 | TB0111A | A016 | 2 | | ALL | |
| 0346 | 22 | | GA | 7-0 | 29-11-22 | D03544 | | 9 | | TB0111A | C016 | 2 | | 001-099 | |
| 0346 | 22 | | GA | 7-0 | 29-11-22 | TB0111A | | C016 | 2 | D03544 | | 9 | | 115-199 | |
| 0347 | 24 | | GK | 3-0 | 33-13-31 | SM00010 | | | 9 | D03410 | | 12 | | 001-099 | |
| 0347 | 24 | | GK | 5-0 | 33-13-31 | SM00010 | | | 9 | D03410 | | 12 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | | 286N2066 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | |
| 0348 | 22 | GA | | | 17-0 | 24-25-11 | D40800J | 24 | | | D03702 | 17 | | | 001-099 |
| 0348 | 22 | GA | | | 18-0 | 24-25-11 | D40800J | 24 | | | D03702 | 17 | | | 115-199 |
| 0349 | 22 | GA | | | 6-0 | 24-25-11 | D03702 | 16 | | | TB0121X | A018 | BJ | | ALL |
| 0352 | 24 | GK | | | 31-0 | 33-13-52 | D07020 | D3 | | | TB0115Y | A018 | BJ | | ALL |
| 0353 | 20 | GA | | | 4-0 | 33-13-52 | D02894 | 8 | | | D07020 | A2 | | | ALL |
| 0354 | 24 | GK | | | 1-0 | 33-13-52 | D07020 | D1 | | | SM00008 | | 9 | | ALL |
| 0355 | 24 | GK | | | 1-0 | 33-13-52 | D07020 | X1 | | | SM00008 | | 9 | | ALL |
| 0356 | 20 | GA | | | 5-0 | 33-13-52 | D07020 | C2 | | | TB0159Z | 11 | BJ | | ALL |
| 0357 | 20 | GA | | | 5-0 | 33-13-52 | D07020 | C1 | | | TB0059Z | 1 | BJ | | ALL |
| 0358 | 20 | GA | | | 5-0 | 33-13-52 | D07020 | B2 | | | TB0159Z | 12 | BJ | | ALL |
| 0359 | 20 | GA | | | 5-0 | 33-13-52 | D06488 | 8 | | | TB0059Z | 2 | BJ | | ALL |
| 0360 | 20 | GA | | | 5-0 | 33-13-52 | D07020 | X2 | | | GD01649 | AC.. | 2 | | ALL |
| 0361 | 24 | GK | | | 12-0 | 33-13-52 | SM00008 | | 9 | | SM00001 | | 9 | | ALL |
| 0362 | 22 | GA | | | 18-0 | 33-51-11 | D40456P | 11 | | | TB0113X | B015 | BJ | | 001-099 |
| 0362 | 22 | GA | | | 19-0 | 33-51-11 | TB0113X | B015 | BJ | | D40456P | 11 | | | 115-199 |
| 0365 | 20 | GA | | | 5-0 | 33-13-52 | TB0101Y | A003 | BJ | | D02890 | 9 | | | 001-099 |
| 0365 | 20 | GA | | | 8-0 | 33-13-52 | TB0101Y | A003 | BJ | | D02890 | 9 | | | 115-199 |
| 0366 | 24 | GK | | | 5-0 | 33-13-52 | D06488 | 12 | | | SM00008 | | 9 | | 001-099 |
| 0366 | 24 | GK | | | 4-0 | 33-13-52 | D06488 | 12 | | | SM00008 | | 9 | | 115-199 |
| 0374 | 20 | GA | | | 5-0 | 33-13-52 | D06488 | 11 | | | GD01649 | AC.. | 2 | | ALL |
| 0375 | 20 | GA | | | 5-0 | 33-13-52 | D06488 | 7 | | | GD01649 | ST.. | 2 | *1 | ALL |
| 0382 | 20 | GA | | | 19-0 | 24-11-11 | D40874P | 50 | | | D41864P | 38 | | | 001-099 |
| 0382 | 20 | GA | | | 12-0 | 24-11-11 | D40874P | 50 | | | D41864P | 38 | | | 115-199 |
| 0383 | 20 | GA | | | 7-0 | 33-13-32 | TB0115Z | 7 | BJ | | D03544 | 1 | | | ALL |
| 0384 | 20 | GA | | | 7-0 | 33-13-32 | TB0115Z | 8 | BJ | | D03544 | 2 | | | 001-099 |
| 0384 | 20 | GA | | | 7-0 | 33-13-32 | D03544 | 2 | | | TB0115Z | 8 | BJ | | 115-199 |
| 0385 | 20 | GA | | | 7-0 | 33-13-32 | TB0115Z | 7 | BJ | | D03500 | 1 | | | ALL |
| 0386 | 20 | GA | | | 7-0 | 33-13-32 | TB0115Z | 8 | BJ | | D03500 | 2 | | | 001-099 |
| 0386 | 20 | GA | | | 7-0 | 33-13-32 | D03500 | 2 | | | TB0115Z | 8 | BJ | | 115-199 |
| 0387 | 20 | GA | | | 7-0 | 33-13-32 | TB0115Z | 7 | BJ | | D03512 | 1 | | | ALL |
| 0388 | 20 | GA | | | 7-0 | 33-13-32 | TB0115Z | 8 | BJ | | D03512 | 2 | | | 001-099 |
| 0388 | 20 | GA | | | 7-0 | 33-13-32 | D03512 | 2 | | | TB0115Z | 8 | BJ | | 115-199 |
| 0389 | 20 | GA | | | 5-0 | 33-13-32 | D04836 | B2 | | | TB0115X | B020 | BJ | | 001-099 |
| 0389 | 20 | GA | | | 8-0 | 33-13-32 | D04836 | B2 | | | TB0115X | B020 | BJ | | 115-199 |
| 0390 | 20 | GA | | | 8-0 | 33-13-32 | TB0115Z | 8 | BJ | | D06872 | 11 | | | 001-099 |
| 0390 | 20 | GA | | | 7-0 | 33-13-32 | D06872 | 11 | | | TB0115Z | 8 | BJ | | 115-199 |
| 0391 | 20 | GA | | | 9-0 | 33-13-32 | D04836 | A2 | | | D02344 | 1 | | | ALL |
| 0392 | 20 | GA | | | 9-0 | 33-13-32 | TB0115Z | 14 | BJ | | D02344 | 2 | | | 001-099 |
| 0392 | 20 | GA | | | 8-0 | 33-13-32 | D02344 | 2 | | | TB0115Z | 14 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|---------|------|--------|-------------|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | | |
| 0395 | 22 | | GA | | 30-0 | 29-11-11 | D03544 | | 12 | | D41870P | | 5 | | ALL | |
| 0396 | 22 | | GA | | 30-0 | 29-11-11 | D03544 | | 11 | | D41870P | | 7 | | ALL | |
| 0397 | 22 | | GA | | 30-0 | 29-11-11 | D03544 | | 10 | | D41870P | | 6 | | ALL | |
| 0400 | 22 | | GA | | 46-0 | 29-11-22 | TB0111A | C016 | 2 | | D40584P | | 15 | | ALL | |
| 0401 | 22 | | GA | | 45-0 | 29-11-22 | D03544 | | 24 | | D40584P | | 16 | | ALL | |
| 0402 | 22 | | GA | | 45-0 | 29-11-22 | D03544 | | 25 | | D40584P | | 17 | | ALL | |
| 0405 | 22 | | GA | | 45-0 | 29-11-31 | D03544 | | 18 | | D40584P | | 18 | | ALL | |
| 0406 | 16 | | GA | | 6-0 | 29-11-31 | D40800J | | 46 | 16 | D03544 | | 17 | 16 | ALL | |
| 0407 | 16 | | GA | | 26-0 | 29-11-31 | D40874P | | 49 | 16 | D40580P | | 2 | 16 | 001-099 | |
| 0407 | 16 | | GA | | 19-0 | 29-11-31 | D40874P | | 49 | 16 | D40580P | | 2 | 16 | 115-199 | |
| 0408 | 24 | | GK | | 48-0 | 29-33-11 | D03544 | | 16 | | D40874P | | 7 | | 001-099 | |
| 0408 | 24 | | GK | | 42-0 | 29-33-11 | D03544 | | 16 | | D40874P | | 7 | | 115-199 | |
| 0409 | 16 | | GA | | 48-0 | 29-11-31 | D40874P | | 51 | 16 | D03544 | | 19 | 16 | 001-099 | |
| 0409 | 16 | | GA | | 42-0 | 29-11-31 | D40874P | | 51 | 16 | D03544 | | 19 | 16 | 115-199 | |
| 0410 | 22 | | GA | | 5-0 | 21-31-21 | D02344 | | | | AB | GD00605 | ST.. | 2 | ALL | |
| 0412 | 20 | | GA | | 5-0 | 33-42-21 | D03503 | | 2 | | | TB0113X | D012 | BJ | ALL | |
| 0413 | 20 | | GA | | 5-0 | 33-42-21 | D03503 | | 1 | | | TB0113X | C012 | BJ | ALL | |
| 0414 | 20 | | GA | | 9-0 | 52-51-11 | D40800J | | 40 | | | TB0116X | C011 | BJ | 001-099 | |
| 0414 | 20 | | GA | | 10-0 | 52-51-11 | D40800J | | 40 | | | TB0116X | C011 | BJ | 115-199 | |
| 0415 | 20 | | GA | | 7-0 | 33-13-32 | D03578 | | 1 | | | TB0116Z | | 22 | BJ | 001-099 |
| 0415 | 20 | | GA | | 8-0 | 33-13-32 | D03578 | | 1 | | | TB0115Z | | 13 | BJ | 115-199 |
| 0416 | 20 | | GA | | 8-0 | 33-13-32 | D03578 | | 2 | | | TB0115Z | | 14 | BJ | ALL |
| 0418 | 24 | | GK | | 30-0 | 21-43-11 | D40800J | | 41 | | | TB0059X | C010 | BJ | 001-099 | |
| 0418 | 24 | | GK | | 31-0 | 21-43-11 | D40800J | | 41 | | | TB0059X | C010 | BJ | 115-199 | |
| 0419 | 24 | | GK | | 43-0 | 21-43-11 | D42074P | | 6 | | | TB0059X | D010 | BJ | ALL | |
| 0420 | 24 | | GK | | 3-0 | 33-13-31 | TB0111Y | C006 | BJ | | | SM00010 | | 9 | 001-099 | |
| 0420 | 24 | | GK | | 5-0 | 33-13-31 | TB0111Y | C006 | BJ | | | SM00010 | | 9 | 115-199 | |
| 0421 | 24 | | GK | | 25-0 | 21-51-11 | D40972P | | 11 | | | D42074P | | 7 | 001-099 | |
| 0421 | 24 | | GK | | 24-0 | 21-51-11 | D40972P | | 11 | | | D42074P | | 7 | 115-199 | |
| 0423 | 22 | | GA | | 7-0 | 33-16-11 | D41000P | | 12 | | | SM00022 | | 9 | 115-199 | |
| 0424 | 22 | | GA | | 12-0 | 33-16-22 | TB0112X | A003 | BJ | | | SM00018 | | 9 | 001-099 | |
| 0424 | 22 | | GA | | 15-0 | 33-16-22 | TB0112X | A003 | BJ | | | SM00018 | | 9 | 115-199 | |
| 0425 | 22 | | GA | | 12-0 | 33-16-22 | TB0112X | A004 | BJ | | | D41002P | | 9 | 001-099 | |
| 0425 | 22 | | GA | | 15-0 | 33-16-22 | TB0112X | A004 | BJ | | | SM00017 | | 9 | 115-199 | |
| 0426 | 22 | | GA | | 12-0 | 33-16-22 | TB0112Y | C009 | BJ | | | SM00019 | | 9 | 001-099 | |
| 0426 | 22 | | GA | | 15-0 | 33-16-22 | TB0112Y | C009 | BJ | | | SM00019 | | 9 | 115-199 | |
| 0427 | 22 | | GA | | 24-0 | 21-44-11 | D41854P | | 13 | | | D42074P | | 9 | 001-099 | |
| 0427 | 22 | | GA | | 22-0 | 21-44-11 | D41854P | | 13 | | | D42074P | | 9 | 115-199 | |
| 0428 | 24 | | GK | | 11-0 | SPARE | D40972P | | 17 | | | D41854P | | 14 | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | | 286N2066 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | |
| 0428 | 24 | GK | | | 10-0 | SPARE | D40972P | | | 17 | D41854P | 14 | | | 115-199 |
| 0429 | 24 | GK | | | 20-0 | 21-61-21 | D40454P | | | 10 | TB0114X | C023 | BJ | | ALL |
| 0430 | 22 | GA | | | 26-0 | SPARE | D41870P | | | 4 | D40584P | 45 | | | ALL |
| 0431 | 24 | GK | | | 19-0 | 21-61-31 | D40456P | | | 10 | TB0111X | C001 | BJ | | 001-099 |
| 0431 | 24 | GK | | | 21-0 | 21-61-31 | D40456P | | | 10 | TB0111X | C001 | BJ | | 115-199 |
| 0434 | 22 | GA | | | 28-0 | 30-32-11 | D40874P | | | 19 | D41870P | 19 | | | 001-099 |
| 0434 | 22 | GA | | | 23-0 | 30-32-11 | D40874P | | | 19 | D41870P | 19 | | | 115-199 |
| 0435 | 22 | GA | | | 28-0 | 30-32-11 | D40874P | | | 20 | D41870P | 20 | | | 001-099 |
| 0435 | 22 | GA | | | 23-0 | 30-32-11 | D40874P | | | 20 | D41870P | 20 | | | 115-199 |
| 0439 | 20 | GA | | | 40-0 | SPARE | D40874P | | | 25 | D41170J | 8 | | | 001-099 |
| 0439 | 20 | GA | | | 23-0 | SPARE | D40874P | | | 25 | D41870P | 8 | | | 115-199 |
| 0440 | 24 | GK | | | 17-0 | 29-33-11 | D40874P | | | 28 | D40584P | 28 | | | 001-099 |
| 0440 | 24 | GK | | | 11-0 | 29-33-11 | D40874P | | | 28 | D40584P | 28 | | | 115-199 |
| 0441 | 20 | GA | | | 40-0 | SPARE | D40874P | | | 32 | D41170J | 10 | | | 001-099 |
| 0441 | 20 | GA | | | 23-0 | SPARE | D40874P | | | 32 | D41870P | 10 | | | 115-199 |
| 0442 | 24 | GK | | | 28-0 | 30-31-11 | D41870P | | | 12 | D40874P | 36 | | | 001-099 |
| 0442 | 24 | GK | | | 23-0 | 30-31-11 | D41870P | | | 12 | D40874P | 36 | | | 115-199 |
| 0443 | 24 | GK | | | 28-0 | 30-31-11 | D41870P | | | 16 | D40874P | 37 | | | 001-099 |
| 0443 | 24 | GK | | | 23-0 | 30-31-11 | D41870P | | | 16 | D40874P | 37 | | | 115-199 |
| 0444 | 24 | GK | | | 28-0 | 30-31-11 | D41870P | | | 17 | D40874P | 38 | | | 001-099 |
| 0444 | 24 | GK | | | 23-0 | 30-31-11 | D41870P | | | 17 | D40874P | 38 | | | 115-199 |
| 0445 | 24 | GK | | | 28-0 | SPARE | D41870P | | | 18 | D40874P | 39 | | | 001-099 |
| 0445 | 24 | GK | | | 23-0 | 30-31-11 | D41870P | | | 18 | D40874P | 39 | | | 115-199 |
| 0446 | 24 | GK | | | 21-0 | 30-31-11 | D41870P | | | 21 | D41854P | 11 | | | 001-099 |
| 0446 | 24 | GK | | | 20-0 | 30-31-11 | D41870P | | | 21 | D41854P | 11 | | | 115-199 |
| 0447 | 24 | GK | | | 21-0 | 30-31-11 | D41870P | | | 22 | D41854P | 15 | | | 001-099 |
| 0447 | 24 | GK | | | 20-0 | 30-31-11 | D41870P | | | 22 | D41854P | 15 | | | 115-199 |
| 0458 | 20 | GA | | | 49-0 | 28-41-11 | D06872 | | | 8 | D40996P | 9 | | | 001-099 |
| 0458 | 20 | GA | | | 51-0 | 28-41-11 | D06872 | | | 8 | D40996P | 9 | | | 115-199 |
| 0475 | 20 | GA | | | 8-0 | 33-13-32 | TB0115X | D020 | BJ | | D06872 | 12 | | | 001-099 |
| 0475 | 20 | GA | | | 8-0 | 33-13-32 | D06872 | | | 12 | TB0115X | D020 | BJ | | 115-199 |
| 0505 | 20 | GA | | | 42-0 | SPARE | D40874P | | | 41 | D03702 | CAP | Y | | 001-099 |
| 0505 | 20 | GA | | | 35-0 | SPARE | D40874P | | | 41 | D03702 | CAP | Y | | 115-199 |
| 0507 | 20 | GA | | | 49-0 | 21-58-13 | D40874P | | | 43 | TB0115X | C019 | BJ | | 001-099 |
| 0507 | 20 | GA | | | 43-0 | 21-58-13 | D40874P | | | 43 | TB0115X | C019 | BJ | | 115-199 |
| 0508 | 20 | GA | | | 46-0 | SPARE | D40874P | | | 44 | D03538 | CAP | Y | | 001-099 |
| 0508 | 20 | GA | | | 40-0 | SPARE | D40874P | | | 44 | D02344 | CAP | Y | | 115-199 |
| 0509 | 20 | GA | | | 46-0 | SPARE | D40874P | | | 45 | D03538 | CAP | Y | | 001-099 |
| 0509 | 20 | GA | | | 40-0 | SPARE | D40874P | | | 45 | D02344 | CAP | Y | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | 286N2066 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0510 | 24 | | GK | | 39-0 | 21-25-11 | | D41854P | 20 | | | D03556 | 10 | | | 001-099 |
| 0510 | 24 | | GK | | 38-0 | 21-25-11 | | D41854P | 20 | | | D03556 | 10 | | | 115-199 |
| 0511 | 20 | | GA | | 46-0 | SPARE | | D40874P | 47 | | | D03538 | CAP | Y | | 001-099 |
| 0511 | 20 | | GA | | 40-0 | SPARE | | D40874P | 47 | | | D03538 | CAP | Y | | 115-199 |
| 0512 | 20 | | GA | | 24-0 | SPARE | | D40874P | 48 | | | D41854P | 28 | | | 001-099 |
| 0512 | 20 | | GA | | 17-0 | SPARE | | D40874P | 48 | | | D41854P | 28 | | | 115-199 |
| 0513 | 22 | | GA | | 41-0 | 29-31-11 | | D40800J | 1 | | | D41854P | 29 | | | 001-099 |
| 0513 | 22 | | GA | | 39-0 | 29-31-11 | | D40800J | 1 | | | D41854P | 29 | | | 115-199 |
| 0516 | 22 | | GA | | 39-0 | 33-16-11 | | D40874P | 52 | | | D41834J | 22 | | | 001-099 |
| 0516 | 22 | | GA | | 33-0 | 33-16-11 | | D40874P | 52 | | | D41834J | 22 | | | 115-199 |
| 0517 | 22 | | GA | | 39-0 | 33-16-11 | | D40874P | 53 | | | D41834J | 23 | | | 001-099 |
| 0517 | 22 | | GA | | 33-0 | 33-16-11 | | D40874P | 53 | | | D41834J | 23 | | | 115-199 |
| 0518 | 22 | | GA | | 39-0 | 33-16-11 | | D40874P | 54 | | | D41834J | 24 | | | 001-099 |
| 0518 | 22 | | GA | | 33-0 | 33-16-11 | | D40874P | 54 | | | D41834J | 24 | | | 115-199 |
| 0519 | 22 | | GA | | 36-0 | 33-16-11 | | D40874P | 55 | | | SM00009 | | 9 | | 001-099 |
| 0519 | 22 | | GA | | 27-0 | 33-16-11 | | D40874P | 55 | | | SM00009 | | 9 | | 115-199 |
| 0521 | 20 | | GA | | 33-0 | 34-61-21 | | D41854P | 17 | | | D41170J | 21 | | | 001-099 |
| 0521 | 20 | | GA | | 10-0 | SPARE | | D41854P | 17 | | | D40972P | 21 | | | 115-199 |
| 0522 | 20 | | GA | | 33-0 | 34-61-21 | | D41854P | 18 | | | D41170J | 22 | | | 001-099 |
| 0522 | 20 | | GA | | 10-0 | SPARE | | D41854P | 18 | | | D40972P | 22 | | | 115-199 |
| 0526 | 24 | | GK | | 25-0 | SPARE | | D40972P | 27 | | | D42074P | 12 | | | 001-099 |
| 0526 | 24 | | GK | | 24-0 | SPARE | | D40972P | 27 | | | D42074P | 12 | | | 115-199 |
| 0527 | 20 | | GA | | 24-0 | SPARE | | D41854P | 23 | | | D42074P | 13 | | | 001-099 |
| 0527 | 20 | | GA | | 22-0 | SPARE | | D41854P | 23 | | | D42074P | 13 | | | 115-199 |
| 0528 | 20 | | GA | | 41-0 | SPARE | | D41854P | 24 | | | D03503 | CAP | Y | | 001-099 |
| 0528 | 20 | | GA | | 39-0 | SPARE | | D41854P | 24 | | | D03503 | CAP | Y | | 115-199 |
| 0529 | 20 | | GA | | 40-0 | SPARE | | D41854P | 25 | | | D06872 | CAP | Y | | 001-099 |
| 0529 | 20 | | GA | | 38-0 | SPARE | | D41854P | 25 | | | D03510 | CAP | Y | | 115-199 |
| 0530 | 20 | | GA | | 41-0 | 21-51-23 | | D40800J | 43 | | | D41854P | 26 | | | 001-099 |
| 0530 | 20 | | GA | | 38-0 | SPARE | | D41854P | 26 | | | D03538 | CAP | Y | | 115-199 |
| 0531 | 20 | | GA | | 35-0 | SPARE | | D41854P | 27 | | | D03702 | CAP | Y | | 001-099 |
| 0531 | 20 | | GA | | 33-0 | SPARE | | D41854P | 27 | | | D03702 | CAP | Y | | 115-199 |
| 0532 | 20 | | GA | | 45-0 | SPARE | | D40584P | 6 | | | D03544 | CAP | Y | | ALL |
| 0533 | 20 | | GA | | 45-0 | SPARE | | D40584P | 7 | | | D03544 | CAP | Y | | ALL |
| 0534 | 20 | | GA | | 46-0 | SPARE | | D40584P | 46 | | | D03503 | CAP | Y | | 001-099 |
| 0534 | 20 | | GA | | 45-0 | SPARE | | D40584P | 46 | | | D03500 | CAP | Y | | 115-199 |
| 0535 | 20 | | GA | | 46-0 | SPARE | | D40584P | 47 | | | D03503 | CAP | Y | | 001-099 |
| 0535 | 20 | | GA | | 45-0 | SPARE | | D40584P | 47 | | | D03500 | CAP | Y | | 115-199 |
| 0537 | 20 | | GA | | 44-0 | SPARE | | D40584P | 53 | | | D03538 | CAP | Y | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | 286N2066 | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | | | |
| 0538 | 20 | GA | | | 39-0 | SPARE | D40584P | 54 | | | D03702 | CAP | Y | | ALL |
| 0539 | 20 | GA | | | 44-0 | SPARE | D40584P | 55 | | | D03538 | CAP | Y | | 001-099 |
| 0539 | 20 | GA | | | 44-0 | SPARE | D40584P | 55 | | | D02344 | CAP | Y | | 115-199 |
| 0540 | 20 | GA | | | 26-0 | SPARE | D41170J | 4 | | | D06872 | CAP | Y | | 001-099 |
| 0540 | 20 | GA | | | 26-0 | SPARE | D41170J | 4 | | | D03584 | CAP | Y | | 115-199 |
| 0541 | 20 | GA | | | 26-0 | SPARE | D41834J | 6 | | | D06872 | CAP | Y | | 001-099 |
| 0541 | 20 | GA | | | 26-0 | SPARE | D41834J | 6 | | | D03584 | CAP | Y | | 115-199 |
| 0542 | 22 | GA | | | 9-0 | 24-51-72 | D03500 | 40 | | | TB0116X | A017 | BJ | | ALL |
| 0543 | 22 | GA | | | 9-0 | 24-51-72 | D03500 | 39 | | | TB0116X | B017 | BJ | | ALL |
| 0544 | 22 | GA | | | 7-0 | 26-18-11 | D03702 | 32 | | | GD00620 | DC.. | 2 | | 001-099 |
| 0544 | 22 | GA | | | 7-0 | 26-18-11 | D03702 | 32 | | | GD00620 | AC.. | 2 | | 115-199 |
| 0545 | 22 | GA | | | 36-0 | 26-18-11 | D03702 | 31 | | | D40972P | 20 | | | 001-099 |
| 0545 | 22 | GA | | | 35-0 | 26-18-11 | D03702 | 31 | | | D40972P | 20 | | | 115-199 |
| 0546 | 20 | GA | | | 28-0 | 28-26-11 | D41870P | 23 | | | D42074P | 14 | | | ALL |
| 0547 | 20 | GA | | | 28-0 | 28-26-11 | D41870P | 24 | | | D42074P | 15 | | | ALL |
| 0548 | 22 | GA | | | 28-0 | 28-26-11 | D41870P | 25 | | | D42074P | 16 | | | ALL |
| 0549 | 22 | GA | | | 28-0 | 28-26-11 | D41870P | 26 | | | D42074P | 17 | | | ALL |
| 0552 | 20 | GA | | | 29-0 | 28-22-11 | D03512 | 12 | | | D41870P | 29 | | | ALL |
| 0553 | 22 | GA | | | 29-0 | SPARE | D03512 | CAP | Y | | D41870P | 30 | | | 115-199 |
| 0557 | 20 | GA | | | 28-0 | SPARE | D40972P | 24 | | | D40996P | 3 | | | 001-099 |
| 0557 | 20 | GA | | | 29-0 | SPARE | D40972P | 24 | | | D40996P | 3 | | | 115-199 |
| 0558 | 22 | GA | | | 5-0 | 21-31-11 | D02344 | | | AC | GD00605 | ST.. | 2 | | ALL |
| 0559 | 22 | GA | | | 49-0 | 28-41-13 | D03512 | 28 | | | D40996P | 25 | | | 001-099 |
| 0559 | 22 | GA | | | 50-0 | 28-41-13 | D03512 | 28 | | | D40996P | 25 | | | 115-199 |
| 0560 | 22 | GA | | | 26-0 | 28-41-13 | D40584P | 37 | | | D40996P | 26 | | | 001-099 |
| 0560 | 22 | GA | | | 27-0 | 28-41-13 | D40584P | 37 | | | D40996P | 26 | | | 115-199 |
| 0561 | 24 | GK | | | 9-0 | 33-24-11 | D40800J | 8 | | | TB0112X | C003 | BJ | | ALL |
| 0563 | 24 | GK | | | 7-0 | 33-11-21 | D40800J | 16 | | | TB0115X | D016 | BJ | | ALL |
| 0564 | 20 | GA | | | 8-0 | 33-13-31 | D04836 | C2 | | | TB0114Z | 11 | BJ | | 001-099 |
| 0564 | 20 | GA | | | 9-0 | 33-13-31 | D04836 | C2 | | | TB0114Z | 11 | BJ | | 115-199 |
| 0565 | 24 | GK | | | 5-0 | 33-13-31 | D04836 | D3 | | | TB0115Y | A018 | BJ | | ALL |
| 0566 | 24 | GK | | | 3-0 | 33-13-31 | D04836 | D1 | | | SM00010 | | 9 | | 001-099 |
| 0566 | 24 | GK | | | 6-0 | 33-13-31 | D04836 | D1 | | | SM00010 | | 9 | | 115-199 |
| 0567 | 20 | GA | | | 3-0 | 33-13-31 | D04836 | C1 | | | SM00005 | | 9 | | 001-099 |
| 0567 | 20 | GA | | | 1-0 | 33-13-31 | D04836 | C1 | | | SM00005 | | 9 | | 115-199 |
| 0568 | 20 | GA | | | 3-0 | 33-13-31 | D04836 | B3 | | | SM00005 | | 9 | | 001-099 |
| 0568 | 20 | GA | | | 1-0 | 33-13-31 | D04836 | B3 | | | SM00005 | | 9 | | 115-199 |
| 0569 | 20 | GA | | | 4-0 | 33-13-31 | D03412 | 2 | | | SM00005 | | 9 | | 001-099 |
| 0569 | 20 | GA | | | 3-0 | 33-13-31 | D03412 | 2 | | | SM00005 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2066 | 286N2066 | | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 0570 | 20 | | GA | | 3-0 | 33-13-31 | D04836 | | A3 | | | SM00005 | | 9 | | 001-099 |
| 0570 | 20 | | GA | | 1-0 | 33-13-31 | D04836 | | A3 | | | SM00005 | | 9 | | 115-199 |
| 0571 | 24 | | GK | | 3-0 | 33-13-31 | D04836 | | X1 | | | SM00010 | | 9 | | 001-099 |
| 0571 | 24 | | GK | | 6-0 | 33-13-31 | D04836 | | X1 | | | SM00010 | | 9 | | 115-199 |
| 0572 | 20 | | GA | | 7-0 | 33-13-31 | D04836 | | X2 | | | GD00603 | AC.. | 2 | | ALL |
| 0573 | 20 | | GA | | 5-0 | 33-13-32 | D04836 | | A1 | | | TB0115X | A020 | BJ | | ALL |
| 0574 | 20 | | GA | | 5-0 | 33-13-32 | D04836 | | B1 | | | TB0115X | A019 | BJ | | ALL |
| 0575 | 18 | | GA | | 9-0 | 73-21-11 | D40800J | 50 | 18 | | | TB0116F | A007 | 2 | | 001-099 |
| 0575 | 18 | | GA | | 29-0 | 73-21-11 | D40800J | 50 | 18 | | | TB0100F | A013 | 2 | | 115-199 |
| 0576 | 18 | | GA | | 9-0 | 73-21-12 | D40800J | 44 | 18 | | | TB0116F | C007 | 2 | | 001-099 |
| 0576 | 18 | | GA | | 29-0 | 73-21-12 | D40800J | 44 | 18 | | | TB0100F | C013 | 2 | | 115-199 |
| 0577 | 18 | | GA | | 29-0 | 28-22-11 | D03512 | 23 | | | | D41870P | 13 | 18 | | ALL |
| 0578 | 18 | | GA | | 29-0 | 28-22-11 | SM00009 | | 9 | | | D41870P | 28 | 18 | | ALL |
| 0579 | 22 | | GA | | 45-0 | SPARE | D41864P | 35 | | | | TB0112X | B015 | BJ | | 001-099 |
| 0580 | 22 | | GA | | 45-0 | SPARE | D41864P | 36 | | | | TB0112X | A015 | BJ | | 001-099 |
| 0601 | 22 | | GA | | 33-0 | 31-31-31 | D40800J | 18 | | | | TB0101X | A007 | BJ | | 115-199 |
| 0800 | 24 | | GK | | 49-0 | 21-33-12 | D40874P | 12 | | | | TB0115Y | A006 | BJ | | 001-099 |
| 0800 | 24 | | GK | | 43-0 | 21-33-12 | D40874P | 12 | | | | TB0115Y | A006 | BJ | | 115-199 |
| 0801 | 22 | | GA | | 9-0 | 24-51-72 | D40800J | 5 | | | | TB0116X | C017 | BJ | | 001-099 |
| 0801 | 22 | | GA | | 10-0 | 24-51-72 | D40800J | 5 | | | | TB0116X | C017 | BJ | | 115-199 |
| 0802 | 24 | | GK | | 28-0 | 21-33-12 | D41834J | 3 | | | | TB0115Y | A006 | BJ | | ALL |
| 0805 | 22 | | GA | | 43-0 | 33-45-11 | D42074P | 18 | | | | TB0059X | A004 | BJ | | ALL |
| 0806 | 20 | | GA | | 16-0 | 33-45-11 | D42074P | 19 | | | | D40996P | 29 | | | 001-099 |
| 0806 | 20 | | GA | | 16-0 | 33-45-11 | D42074P | 19 | | | | D40996P | 19 | | | 115-199 |
| 0807 | 20 | | GA | | 16-0 | 33-45-11 | D42074P | 20 | | | | D40996P | 20 | | | ALL |
| 0808 | 20 | | GA | | 7-0 | 33-13-32 | TB0115Z | 8 | BJ | | | GD00602 | AC.. | 2 | | ALL |
| 1001 | 24 | | G1 | AM | 7-0 | 21-31-21 | D02344 | 28 | | | | TB0113X | A016 | BJ | | ALL |
| 1001Z | | | | AM | 0-0 | 21-31-21 | D02344 | DED | | | | TB0113X | DED | | | ALL |
| 1002 | 24 | | G1 | AN | 44-0 | 21-31-21 | D02344 | 25 | | | | D40584P | 3 | | | ALL |
| 1002Z | | | | AN | 0-0 | 21-31-21 | D02344 | DED | | | | D40584P | DED | | | ALL |
| 1003 | 20 | | GT | BA | 46-0 | 21-31-21 | D02344 | 15 | | | | D41864P | 12 | | | ALL |
| 1003Z | | | | BA | 0-0 | 21-31-21 | D02344 | DED | | | | D41864P | DED | | | ALL |
| 1004 | 24 | | G1 | AY | 46-0 | 21-31-21 | D02344 | 24 | | | | D41864P | 19 | | | ALL |
| 1004Z | | | | AY | 0-0 | 21-31-21 | D02344 | DED | | | | D41864P | DED | | | ALL |
| 1005 | 24 | | G1 | AZ | 46-0 | 21-31-21 | D02344 | 12 | | | | D41864P | 22 | | | ALL |
| 1005Z | | | | AZ | 0-0 | 21-31-21 | D02344 | DED | | | | D41864P | DED | | | ALL |
| 1006 | 18 | | GT | BB | 39-0 | 25-31-33 | D03500 | 7 | 18 | | | D41854P | 2 | 18 | | 115-199 |
| 1006Z | | | | BB | 0-0 | 25-31-33 | D03500 | DED | | | | D41854P | DED | | | 115-199 |
| 1007 | 18 | | GT | BC | 9-0 | 25-31-33 | D40580P | 18 | 18 | | | D41854P | 12 | 18 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 1007Z | | | | BC | 0-0 | 25-31-33 | D40580P | DED | | | D41854P | DED | | | 115-199 |
| 1011 | 20 | GT | | CA | 6-0 | 27-21-11 | D01744 | 11 | | | TB0158X | D003 | BJ | | 115-199 |
| 1011Z | | | | CA | 0-0 | 27-21-11 | D01744 | DED | | | TB0158X | DED | | | 115-199 |
| 1012 | 20 | GT | | CB | 6-0 | 27-21-11 | D01744 | 6 | | | TB0158X | B003 | BJ | | 115-199 |
| 1012Z | | | | CB | 0-0 | 27-21-11 | D01744 | DED | | | TB0158X | DED | | | 115-199 |
| 1013 | 20 | GT | | CC | 6-0 | 27-21-11 | D01744 | 14 | | | TB0158X | C003 | BJ | | 115-199 |
| 1013Z | | | | CC | 0-0 | 27-21-11 | D01744 | DED | | | TB0158X | DED | | | 115-199 |
| 2001B | 24 | GL | | AJ | 51-0 | SPARE | D03510 | 32 | | | D40996P | 4 | | | 115-199 |
| 2001R | 24 | GL | | AJ | 0-0 | SPARE | D03510 | 16 | | | D40996P | 24 | | | 115-199 |
| 2002B | 24 | GL | | AW | 41-0 | 27-28-13 | D01876 | 9 | | | D40584P | 30 | | | 001-099 |
| 2002B | 22 | GB | | AW | 41-0 | 27-28-13 | D01876 | 9 | | | D40584P | 30 | | | 115-199 |
| 2002R | 24 | GL | | AW | 0-0 | 27-28-13 | D01876 | 10 | | | D40584P | 31 | | | 001-099 |
| 2002R | 22 | GB | | AW | 0-0 | 27-28-13 | D01876 | 10 | | | D40584P | 31 | | | 115-199 |
| 2003B | 24 | GL | | AA | 46-0 | 36-21-11 | D03538 | 18 | | | D40874P | 1 | | | 001-099 |
| 2003B | 24 | GL | | AA | 40-0 | 36-21-11 | D03538 | 18 | | | D40874P | 1 | | | 115-199 |
| 2003R | 24 | GL | | AA | 0-0 | 36-21-11 | D03538 | 17 | | | D40874P | 2 | | | ALL |
| 2004B | 24 | GL | | AR | 44-0 | 28-41-14 | D40996P | 17 | | | D03702 | 13 | | | 001-099 |
| 2004B | 24 | GL | | AR | 45-0 | 28-41-14 | D40996P | 17 | | | D03702 | 13 | | | 115-199 |
| 2004R | 24 | GL | | AR | 0-0 | 28-41-14 | D40996P | 18 | | | D03702 | 15 | | | ALL |
| 2005B | 24 | GL | | AP | 51-0 | SPARE | D03510 | 12 | | | D40996P | 5 | | | 115-199 |
| 2005R | 24 | GL | | AP | 0-0 | SPARE | D03510 | 11 | | | D40996P | 7 | | | 115-199 |
| 2006B | 24 | GL | | AK | 51-0 | SPARE | D03510 | 29 | | | D40996P | 21 | | | 115-199 |
| 2006R | 24 | GL | | AK | 0-0 | SPARE | D03510 | 13 | | | D40996P | 6 | | | 115-199 |
| 2007B | 24 | GL | | AQ | 51-0 | SPARE | D03510 | 10 | | | D40996P | 13 | | | 115-199 |
| 2007R | 24 | GL | | AQ | 0-0 | SPARE | D03510 | 24 | | | D40996P | 16 | | | 115-199 |
| 2008B | 24 | GL | | AL | 51-0 | SPARE | D03510 | 20 | | | D40996P | CAP | Y | | 115-199 |
| 2008R | 24 | GL | | AL | 0-0 | SPARE | D03510 | 39 | | | D40996P | CAP | Y | | 115-199 |
| 2009B | 24 | GL | | AG | 51-0 | SPARE | D03510 | 19 | | | D40996P | CAP | Y | | 115-199 |
| 2009R | 24 | GL | | AG | 0-0 | SPARE | D03510 | 18 | | | D40996P | CAP | Y | | 115-199 |
| 2010B | 18 | GB | | AX | 51-0 | 28-43-11 | SP01930 | | 9 | | D40996P | 14 | 18 | | 115-199 |
| 2010R | 18 | GB | | AX | 0-0 | 28-43-11 | SP01932 | | 9 | | D40996P | 12 | 18 | | 115-199 |
| 2011B | 24 | GL | | BE | 8-0 | 21-65-11 | D03578 | 5 | | | D03154 | A | | | ALL |
| 2011R | 24 | GL | | BE | 0-0 | 21-65-11 | D03578 | 6 | | | SM00020 | | 9 | | ALL |
| 2012B | 24 | GL | | BF | 20-0 | 21-65-11 | D40454P | 7 | | | D03578 | 7 | | | 001-099 |
| 2012B | 24 | GL | | BF | 19-0 | 21-65-11 | D40454P | 7 | | | D03578 | 7 | | | 115-199 |
| 2012R | 24 | GL | | BF | 0-0 | 21-65-11 | D40454P | 8 | | | D03578 | 8 | | | ALL |
| 2013B | 24 | GL | | BG | 20-0 | 21-65-11 | D40456P | 7 | | | D03578 | 9 | | | ALL |
| 2013R | 24 | GL | | BG | 0-0 | 21-65-11 | D40456P | 8 | | | D03578 | 10 | | | ALL |
| 2014B | 24 | GL | | BH | 49-0 | 28-41-13 | D03512 | 26 | | | D40996P | 27 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 22

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 2014B | 22 | GB | BH | | 50-0 | 28-41-13 | D03512 | | 26 | | D40996P | 27 | | | 115-199 |
| 2014R | 24 | GL | BH | | 0-0 | 28-41-13 | D03512 | | 24 | | D40996P | 28 | | | 001-099 |
| 2014R | 22 | GB | BH | | 0-0 | 28-41-13 | D03512 | | 24 | | D40996P | 28 | | | 115-199 |
| 2017B | 22 | GB | AD | | 32-0 | 29-11-31 | D40580P | | 7 | | TB0121X | C004 | BJ | | 115-199 |
| 2017R | 22 | GB | AD | | 0-0 | 29-11-31 | D40580P | | 8 | | TB0121X | D004 | BJ | | 115-199 |
| 2018B | 22 | GB | BD | | 32-0 | 29-11-22 | D40580P | | 6 | | TB0121X | C003 | BJ | | 115-199 |
| 2018R | 22 | GB | BD | | 0-0 | 29-11-22 | D40580P | | 5 | | TB0121X | D003 | BJ | | 115-199 |
| 2019B | 22 | GB | BJ | | 5-0 | 29-11-12 | D03708 | | 20 | | TB0121X | A004 | BJ | | 115-199 |
| 2019R | 22 | GB | BJ | | 0-0 | 29-11-12 | D03708 | | 21 | | TB0121X | B004 | BJ | | 115-199 |
| 2021B | 24 | PL | BP | | 20-0 | 23-51-21 | D41170J | | 30 | | TB0058X | A007 | BJ | | 115-199 |
| 2021R | 24 | PL | BP | | 0-0 | 23-51-21 | D41170J | | 31 | | TB0058X | A008 | BJ | | 115-199 |
| 2022B | 24 | PL | BQ | | 20-0 | 23-51-11 | D41834J | | 30 | | TB0059X | A014 | BJ | | 115-199 |
| 2022R | 24 | PL | BQ | | 0-0 | 23-51-11 | D41834J | | 31 | | TB0059X | A015 | BJ | | 115-199 |
| 2509B | 22 | GU | AG | | 49-0 | 28-41-11 | D06872 | | 5 | | D40996P | 23 | | | 001-099 |
| 2509B | 22 | GU | GA | | 50-0 | 28-41-11 | D06872 | | 5 | | D40996P | 23 | | | 115-199 |
| 2509R | 22 | GU | AG | | 0-0 | 28-41-11 | D06872 | | 6 | | D40996P | 22 | | | 001-099 |
| 2509R | 22 | GU | GA | | 0-0 | 28-41-11 | D06872 | | 6 | | D40996P | 22 | | | 115-199 |
| 2509Z | | | AG | | 0-0 | 28-41-11 | GD00603 | ST.. | 2 | | D40996P | 10 | | | 001-099 |
| 2509Z | | | GA | | 0-0 | 28-41-11 | GD00603 | ST.. | 2 | | D40996P | 10 | | | 115-199 |
| 3001B | 24 | GM | AF | | 12-0 | 33-13-52 | D02894 | | 5 | | SM00003 | | 9 | | ALL |
| 3001R | 24 | GM | AF | | 0-0 | 33-13-52 | D02894 | | 6 | | SM00002 | | 9 | | ALL |
| 3001Y | 24 | GM | AF | | 0-0 | 33-13-52 | D02894 | | 1 | | SM00004 | | 9 | | ALL |
| 3002B | 24 | GM | AS | | 20-0 | 33-13-51 | D03503 | | 12 | | SM00003 | | 9 | | 001-099 |
| 3002B | 24 | GM | AS | | 21-0 | 33-13-51 | D03503 | | 12 | | SM00003 | | 9 | | 115-199 |
| 3002R | 24 | GM | AS | | 0-0 | 33-13-51 | D03503 | | 9 | | SM00002 | | 9 | | ALL |
| 3002Y | 24 | GM | AS | | 0-0 | 33-13-51 | D03503 | | 11 | | SM00004 | | 9 | | ALL |
| 3003B | 24 | GM | AT | | 13-0 | 33-13-51 | D02892 | | 5 | | SM00003 | | 9 | | 001-099 |
| 3003B | 24 | GM | AT | | 11-0 | 33-13-51 | D02892 | | 5 | | SM00003 | | 9 | | 115-199 |
| 3003R | 24 | GM | AT | | 0-0 | 33-13-51 | D02892 | | 6 | | SM00002 | | 9 | | ALL |
| 3003Y | 24 | GM | AT | | 0-0 | 33-13-51 | D02892 | | 1 | | SM00004 | | 9 | | ALL |
| 3004B | 24 | GM | AU | | 15-0 | 33-13-52 | D02890 | | 5 | | SM00003 | | 9 | | 001-099 |
| 3004B | 24 | GM | AU | | 13-0 | 33-13-52 | D02890 | | 5 | | SM00003 | | 9 | | 115-199 |
| 3004R | 24 | GM | AU | | 0-0 | 33-13-52 | D02890 | | 6 | | SM00002 | | 9 | | ALL |
| 3004Y | 24 | GM | AU | | 0-0 | 33-13-52 | D02890 | | 1 | | SM00004 | | 9 | | ALL |
| 3005B | 22 | GC | AV | | 45-0 | 21-31-31 | D40874P | | 4 | | TB0112X | D015 | BJ | | 001-099 |
| 3005B | 22 | GC | AV | | 39-0 | 21-31-31 | D40874P | | 4 | | TB0112X | D015 | BJ | | 115-199 |
| 3005R | 22 | GC | AV | | 0-0 | 21-31-31 | D40874P | | 5 | | TB0112X | C016 | BJ | | ALL |
| 3005Y | 22 | GC | AV | | 0-0 | 21-31-31 | D40874P | | 3 | | TB0112X | C015 | BJ | | ALL |
| 3006B | 24 | GM | AD | | 3-0 | 33-13-31 | SM00013 | | 9 | | D03412 | 5 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 23

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2066 | 286N2066 | | | FLIGHT DECK TO E/E BAY CAT "L2" SYSTEM (continued) | | | | | | | | | | | |
| 3006B | 24 | GM | CF | 3-0 | 33-13-31 | D03412 | | 5 | | | SM00013 | | 9 | | 115-199 |
| 3006R | 24 | GM | AD | 0-0 | 33-13-31 | SM00014 | | | 9 | | D03412 | 6 | | | 001-099 |
| 3006R | 24 | GM | CF | 0-0 | 33-13-31 | D03412 | | 6 | | | SM00014 | | 9 | | 115-199 |
| 3006Y | 24 | GM | AD | 0-0 | 33-13-31 | SM00012 | | | 9 | | D03412 | 1 | | | 001-099 |
| 3006Y | 24 | GM | CF | 0-0 | 33-13-31 | D03412 | | 1 | | | SM00012 | | 9 | | 115-199 |
| 3007B | 24 | GM | AE | 3-0 | 33-13-31 | SM00013 | | | 9 | | D03410 | 5 | | | 001-099 |
| 3007B | 24 | GM | AE | 2-0 | 33-13-31 | SM00013 | | | 9 | | D03410 | 5 | | | 115-199 |
| 3007R | 24 | GM | AE | 0-0 | 33-13-31 | SM00014 | | | 9 | | D03410 | 6 | | | ALL |
| 3007Y | 24 | GM | AE | 0-0 | 33-13-31 | SM00012 | | | 9 | | D03410 | 1 | | | ALL |
| 3008B | 24 | GM | BD | 3-0 | 33-13-31 | TB0111Y | C005 | | BJ | | SM00013 | | 9 | | 001-099 |
| 3008B | 24 | GM | BK | 4-0 | 33-13-31 | SM00013 | | | | | TB0111Y | C005 | BJ | | 115-199 |
| 3008R | 24 | GM | BD | 0-0 | 33-13-31 | TB0111Y | A006 | | BJ | | SM00014 | | 9 | | 001-099 |
| 3008R | 24 | GM | BK | 0-0 | 33-13-31 | SM00014 | | | 9 | | TB0111Y | A006 | BJ | | 115-199 |
| 3008Y | 24 | GM | BD | 0-0 | 33-13-31 | TB0111Y | A005 | | BJ | | SM00012 | | 9 | | 001-099 |
| 3008Y | 24 | GM | BK | 0-0 | 33-13-31 | SM00012 | | | 9 | | TB0111Y | A005 | BJ | | 115-199 |
| 3009B | 24 | GM | BM | 13-0 | 33-13-52 | D06488 | | 5 | | | SM00003 | | 9 | | 001-099 |
| 3009B | 24 | GM | BM | 12-0 | 33-13-52 | D06488 | | 5 | | | SM00003 | | 9 | | 115-199 |
| 3009R | 24 | GM | BM | 0-0 | 33-13-52 | D06488 | | 6 | | | SM00002 | | 9 | | ALL |
| 3009Y | 24 | GM | BM | 0-0 | 33-13-52 | D06488 | | 1 | | | SM00004 | | 9 | | ALL |
| 3013B | 24 | GM | AH | 27-0 | 33-13-41 | D03503 | | 7 | | | D41170J | 2 | | | ALL |
| 3013R | 24 | GM | AH | 0-0 | 33-13-41 | D03503 | | 8 | | | D41170J | 1 | | | ALL |
| 3013Y | 24 | GM | AH | 0-0 | 33-13-41 | D03503 | | 10 | | | D41170J | 7 | | | ALL |
| 4251B | 22 | GW | AC | 46-0 | 21-31-11 | D02344 | | 9 | | | D41864P | 16 | | | ALL |
| 4251G | 22 | GW | AC | 0-0 | 21-31-11 | D02344 | | 8 | | | D41864P | 14 | | | ALL |
| 4251R | 22 | GW | AC | 0-0 | 21-31-11 | D02344 | | 21 | | | D41864P | 17 | | | ALL |
| 4251Y | 22 | GW | AC | 0-0 | 21-31-11 | D02344 | | 20 | | | D41864P | 15 | | | ALL |
| 4251Z | | | AC | 0-0 | 21-31-11 | D02344 | | | | AC | D41864P | 13 | | | ALL |
| 4252B | 22 | GW | AB | 46-0 | 21-31-21 | D02344 | | 11 | | | D41864P | 30 | | | ALL |
| 4252G | 22 | GW | AB | 0-0 | 21-31-21 | D02344 | | 10 | | | D41864P | 31 | | | ALL |
| 4252R | 22 | GW | AB | 0-0 | 21-31-21 | D02344 | | 23 | | | D41864P | 32 | | | ALL |
| 4252Y | 22 | GW | AB | 0-0 | 21-31-21 | D02344 | | 22 | | | D41864P | 33 | | | ALL |
| 4252Z | | | AB | 0-0 | 21-31-21 | D41864P | | 34 | | | D02344 | | | AB | 001-099 |
| 4252Z | | | AB | 0-0 | 21-31-21 | D02344 | | | | AB | D41864P | 34 | | | 115-199 |
| FRAC | | | | 0-0 | 21-31-11 | D02344 | | | | AC | D02344 | 14 | | | 001-099 |
| FRAC | | | | 1-0 | 21-31-11 | D02344 | | | | AC | D02344 | 14 | | | 115-199 |
| PA01 | | | | 0-0 | 33-13-31 | D04836 | | G1 | | | D04836 | G3 | | | ALL |
| W2067 | 286N2067 | | | DFDAU IDU TO E3-3 | | | | | | | | | | | |
| 0001 | 22 | GA | | 36-0 | 31-31-02 | D01823 | | A | | | D40255P | 7 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 24

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|-------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2067 | 286N2067 | | | DFDAU IDU TO E3-3 (continued) | | | | | | | | | | | |
| 0002 | 20 | | GA | | 6-0 | 31-31-02 | D01823 | | B | | GD02303 | AC.. | 2 | | 001-099 |
| 0003 | 20 | | GA | | 6-0 | 31-31-02 | D01823 | | | FA | GD02303 | ST.. | 2 | | 001-099 |
| 0004 | 20 | | GA | | 6-0 | 31-31-02 | D01823 | | | FB | GD02303 | ST.. | 2 | | 001-099 |
| 0005 | 24 | | GK | | 36-0 | 31-31-02 | D07658 | | H | | D40255P | | 8 | | 001-099 |
| 0006 | 20 | | GA | | 6-0 | 31-31-02 | D07658 | | | FD | GD02303 | ST.. | 2 | | 001-099 |
| 0007 | 20 | | GA | | 6-0 | 31-31-02 | D07658 | | | FC | GD02303 | ST.. | 2 | | 001-099 |
| 0008 | 20 | | GA | | 6-0 | 31-31-02 | D07658 | | P | | GD02303 | DC.. | 2 | | 001-099 |
| 0009 | 20 | | GA | | 6-0 | 31-31-02 | D07658 | | E | | GD02303 | DC.. | 2 | | 001-099 |
| 0010 | 20 | | GA | | 6-0 | 31-31-02 | D07658 | | F | | GD02303 | ST.. | 2 | | 001-099 |
| 0011 | 22 | | GA | | 36-0 | 31-31-02 | D07658 | | A | | D40255P | | 16 | | 001-099 |
| 0012 | 20 | | GA | | 6-0 | 31-31-02 | D07658 | | C | | GD02303 | AC.. | 2 | | 001-099 |
| 2501B | 24 | | G2 | AA | 36-0 | 31-31-02 | D01823 | | B- | | D40255P | | 4 | | 001-099 |
| 2501R | 24 | | G2 | AA | 0-0 | 31-31-02 | D01823 | | A- | | D40255P | | 5 | | 001-099 |
| 2501Z | | | | AA | 0-0 | 31-31-02 | D01823 | | | FA | D40255P | | 6 | | 001-099 |
| 2502B | 24 | | G2 | AB | 36-0 | 31-31-02 | D01823 | | D- | | D40255P | | 1 | | 001-099 |
| 2502R | 24 | | G2 | AB | 0-0 | 31-31-02 | D01823 | | C- | | D40255P | | 2 | | 001-099 |
| 2502Z | | | | AB | 0-0 | 31-31-02 | D01823 | | | FB | D40255P | | 3 | | 001-099 |
| 2503B | 24 | | G2 | AC | 36-0 | 31-31-02 | D07658 | | M | | D40255P | | 13 | | 001-099 |
| 2503R | 24 | | G2 | AC | 0-0 | 31-31-02 | D07658 | | K | | D40255P | | 14 | | 001-099 |
| 2503Z | | | | AC | 0-0 | 31-31-02 | D07658 | | | FC | D40255P | | 15 | | 001-099 |
| 3501B | 24 | | G3 | AD | 36-0 | 31-31-02 | D07658 | | D | | D40255P | | 9 | | 001-099 |
| 3501R | 24 | | G3 | AD | 0-0 | 31-31-02 | D07658 | | R | | D40255P | | 10 | | 001-099 |
| 3501Y | 24 | | G3 | AD | 0-0 | 31-31-02 | D07658 | | G | | D40255P | | 11 | | 001-099 |
| 3501Z | | | | AD | 0-0 | 31-31-02 | D07658 | | | FD | D40255P | | 12 | | 001-099 |
| W2069 | 286N2069 | | | VHF-C CONTROL, P8 TO E4-4 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 33-13-52 | D00891 | | 1 | | TB0059Z | | 1 | BJ | 001-099 |
| 0002 | 20 | | GA | | 5-0 | 33-13-52 | D00891 | | 2 | | GD02303 | AC.. | 2 | | 001-099 |
| 0003 | 18 | | GA | | 46-0 | 23-12-31 | D00891 | | 13 | 18 | D41529J | | 7 | | 001-099 |
| 0005 | 24 | | GK | | 46-0 | 23-12-31 | D00891 | | 5 | | D41529J | | 5 | | 001-099 |
| 0006 | 24 | | GK | | 46-0 | 23-12-31 | D00891 | | 6 | | D41529J | | 6 | | 001-099 |
| 0007 | 24 | | GK | | 46-0 | 23-12-31 | D00891 | | 7 | | D41529J | | 1 | | 001-099 |
| 0008 | 24 | | GK | | 46-0 | 23-12-31 | D00891 | | 8 | | D41529J | | 8 | | 001-099 |
| 0009 | 24 | | GK | | 46-0 | 23-12-31 | D00891 | | 9 | | D41529J | | 9 | | 001-099 |
| 0010 | 20 | | GA | | 5-0 | 23-12-31 | D00891 | | 14 | | GD02303 | DC.. | 2 | | 001-099 |
| 5001B | 24 | | G2 | AA | 46-0 | 23-12-31 | D00891 | | 18 | | D41529J | | 12 | | 001-099 |
| 5001R | 24 | | G2 | AA | 0-0 | 23-12-31 | D00891 | | 17 | | D41529J | | 11 | | 001-099 |
| 5001Z | | | | AA | 0-0 | 23-12-31 | D00891 | | 19 | | D41529J | | 3 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2060

Page 25 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM | | | | | | | | | | | |
| 0001 | 22 | | GA | | 38-0 | 24-22-21 | D03710 | | 13 | | D40598P | | 11 | | 001-003, 115-199 |
| 0002 | 22 | | GA | | 38-0 | 24-22-21 | D03710 | | 12 | | D40598P | | 12 | | 001-003, 115-199 |
| 0003 | 22 | | GA | | 33-0 | 27-23-11 | D03710 | | 8 | | D42176P | | 12 | | 001-099 |
| 0003 | 22 | | GA | | 43-0 | 27-23-11 | D03710 | | 8 | | D41876P | | 27 | | 115-199 |
| 0004 | 22 | | GA | | 33-0 | 27-23-11 | D03710 | | 10 | | D42176P | | 24 | | 001-099 |
| 0004 | 22 | | GA | | 43-0 | 27-23-11 | D03710 | | 10 | | D41876P | | 28 | | 115-199 |
| 0005 | 22 | | GA | | 33-0 | 27-23-11 | D03710 | | 7 | | D42176P | | 25 | | 001-099 |
| 0005 | 22 | | GA | | 43-0 | 27-23-11 | D03710 | | 7 | | D41876P | | 29 | | 115-199 |
| 0006 | 22 | | GA | | 12-0 | 27-23-11 | D03710 | | 9 | | D40802J | | 10 | | ALL |
| 0009 | 22 | | GA | | 16-0 | 30-41-12 | D03704 | | 37 | | TB0113X | A011 | BJ | | ALL |
| 0011 | 18 | | GA | | 27-0 | 30-42-11 | D03520 | | 10 | | D41172J | | 21 | | 001-099 |
| 0011 | 18 | | GA | | 25-0 | 30-42-11 | D03520 | | 10 | | D41172J | | 21 | | 115-199 |
| 0012 | 18 | | GA | | 27-0 | 30-42-11 | D03520 | | 4 | | D41172J | | 23 | | 001-099 |
| 0012 | 18 | | GA | | 25-0 | 30-42-11 | D03520 | | 4 | | D41172J | | 23 | | 115-199 |
| 0014 | 24 | | GK | | 17-0 | 24-11-21 | D41058P | | 18 | | D40598P | | 33 | | 001-099 |
| 0014 | 24 | | GK | | 16-0 | 24-11-21 | D41058P | | 18 | | D40598P | | 33 | | 115-199 |
| 0015 | 20 | | GA | | 29-0 | SPARE | D41470P | | 28 | | D40590P | | 4 | | ALL |
| 0016 | 22 | | GA | | 33-0 | SPARE | D41470P | | 32 | | D41876P | | 25 | | ALL |
| 0017 | 22 | | GA | | 9-0 | 23-43-11 | D40802J | | 24 | | TB0113X | A002 | BJ | | ALL |
| 0018 | 20 | | GA | | 9-0 | 25-31-11 | D40802J | | 25 | | D03502 | | 6 | | 001-099 |
| 0018 | 20 | | GA | | 9-0 | 25-31-21 | D03502 | | 6 | | D40802J | | 2 | | 115-199 |
| 0019 | 20 | | GA | | 9-0 | SPARE | D03502 | | 18 | | D40802J | | 1 | | 115-199 |
| 0020 | 22 | | GA | | 17-0 | 33-16-31 | SM00008 | | 9 | | D41172J | | 9 | | 001-099 |
| 0020 | 22 | | GA | | 15-0 | 33-16-31 | SM00008 | | 9 | | D41172J | | 9 | | 115-199 |
| 0021 | 22 | | GA | | 19-0 | 33-16-31 | SM00008 | | 9 | | TB0100X | A003 | BJ | | 001-099 |
| 0021 | 22 | | GA | | 18-0 | 33-16-31 | SM00008 | | 9 | | TB0100X | A003 | BJ | | 115-199 |
| 0022 | 18 | | GA | | 39-0 | 28-22-11 | D03514 | | 15 | | D41856P | | 39 | 18 | 001-099 |
| 0022 | 18 | | GA | | 38-0 | 28-22-11 | D03514 | | 15 | | D41856P | | 39 | 18 | 115-199 |
| 0024 | 22 | | GA | | 17-0 | 33-16-41 | SM00011 | | 9 | | D41172J | | 11 | | 001-099 |
| 0024 | 22 | | GA | | 15-0 | 33-16-41 | SM00011 | | 9 | | D41172J | | 11 | | 115-199 |
| 0025 | 22 | | GA | | 17-0 | 33-16-41 | SM00010 | | 9 | | D41172J | | 12 | | 001-099 |
| 0025 | 22 | | GA | | 15-0 | 33-16-41 | SM00010 | | 9 | | D41172J | | 12 | | 115-199 |
| 0026 | 22 | | GA | | 17-0 | 33-16-41 | SM00009 | | 9 | | D41172J | | 13 | | 001-099 |
| 0026 | 22 | | GA | | 15-0 | 33-16-41 | SM00009 | | 9 | | D41172J | | 13 | | 115-199 |
| 0027 | 22 | | GA | | 19-0 | 33-16-41 | SM00012 | | 9 | | TB0100X | C003 | BJ | | 001-099 |
| 0027 | 22 | | GA | | 18-0 | 33-16-41 | SM00012 | | 9 | | TB0100X | C003 | BJ | | 115-199 |
| 0029 | 22 | | GA | | 20-0 | 33-16-41 | TB0058X | A001 | BJ | | SM00009 | | 9 | | 115-199 |
| 0030 | 24 | | GK | | 16-0 | SPARE | D40598P | | 1 | | D41058P | | 19 | | 115-199 |
| 0031 | 24 | | GK | | 17-0 | 24-11-21 | D40598P | | 2 | | D41058P | | 20 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0031 | 24 | | GK | | 16-0 | 24-11-21 | D40598P | | 2 | | D41058P | 20 | | | 115-199 |
| 0033 | 22 | | GA | | 39-0 | 22-21-11 | D03704 | | 2 | | D40598P | 23 | | | ALL |
| 0034 | 22 | | GA | | 6-0 | 30-41-12 | D03704 | | 36 | | GD00617 | DC.. | 2 | | 001-099 |
| 0034 | 20 | | GA | | 6-0 | 30-41-12 | D03704 | | 36 | | GD00617 | DC.. | 2 | | 115-199 |
| 0035 | 20 | | GA | | 6-0 | 22-21-11 | D03704 | | 23 | | GD00617 | ST.. | 2 | | ALL |
| 0036 | 20 | | GA | | 39-0 | 34-33-21 | D40598P | | 24 | | D03704 | CAP | Y | | 001-099 |
| 0036 | 20 | | GA | | 39-0 | 34-33-21 | D03704 | CAP | Y | | D40598P | 24 | | | 115-199 |
| 0037 | 20 | | GA | | 6-0 | 22-21-11 | D03704 | | 1 | | GD00617 | DC.. | 2 | | ALL |
| 0039 | 22 | | GA | | 17-0 | 33-16-41 | D41006P | | 10 | | D41172J | 10 | | | 001-099 |
| 0039 | 22 | | GA | | 16-0 | 33-16-41 | D41006P | | 10 | | D41172J | 10 | | | 115-199 |
| 0040 | 20 | | GA | | 6-0 | 24-22-21 | D03710 | | 22 | | GD00617 | ST.. | 2 | | 001-003 |
| 0040 | 20 | | GA | | 5-0 | 24-22-21 | D03710 | | 22 | | GD00617 | ST.. | 2 | | 115-199 |
| 0041 | 22 | | GA | | 17-0 | SPARE | D40590P | | 16 | | D41058P | 22 | | | 115-199 |
| 0044 | 24 | | GK | | 24-0 | 34-22-26 | D40802J | | 5 | | TB0100X | C001 | BJ | | ALL |
| 0045 | 20 | | GA | | 34-0 | 30-31-12 | D42176P | | 28 | | D02762 | =A | | | 001-099 |
| 0046 | 20 | | GA | | 34-0 | 30-31-12 | D42176P | | 29 | | D02762 | =B | | | 001-099 |
| 0047 | 20 | | GA | | 34-0 | 30-31-12 | D42176P | | 30 | | D02764 | =A | | | 001-099 |
| 0048 | 20 | | GA | | 34-0 | 30-31-12 | D42176P | | 31 | | D02764 | =B | | | 001-099 |
| 0050 | 22 | | GA | | 33-0 | 26-18-21 | D03540 | | 5 | | D40970P | 6 | | | 001-099 |
| 0050 | 24 | | GK | | 31-0 | 26-18-21 | D03540 | | 5 | | D40970P | 6 | | | 115-199 |
| 0051 | 24 | | GK | | 22-0 | 36-11-22 | D41860P | | 3 | | D41058P | 3 | | | 001-099 |
| 0051 | 24 | | GK | | 21-0 | 36-11-22 | D41860P | | 3 | | D41058P | 3 | | | 115-199 |
| 0052 | 22 | | GA | | 44-0 | 33-14-41 | D41470P | | 19 | | TB0114X | B014 | BJ | | 001-099 |
| 0052 | 22 | | GA | | 45-0 | 33-14-41 | D41470P | | 19 | | TB0114X | B014 | BJ | | 115-199 |
| 0053 | 22 | | GA | | 24-0 | 24-22-21 | D40598P | | 38 | | D40592P | 2 | | | ALL |
| 0054 | 22 | | GA | | 41-0 | 24-22-21 | D03502 | | 24 | | D40592P | 3 | | | 001-099 |
| 0054 | 22 | | GA | | 43-0 | 24-22-21 | D03502 | | 24 | | D40592P | 3 | | | 115-199 |
| 0058 | 22 | | GA | | 45-0 | 29-32-11 | D03546 | | 14 | | D41058P | 25 | | | 001-099 |
| 0058 | 22 | | GA | | 44-0 | 29-32-11 | D03546 | | 14 | | D41058P | 25 | | | 115-199 |
| 0059 | 22 | | GA | | 45-0 | 29-32-11 | D03546 | | 13 | | D41058P | 24 | | | 001-099 |
| 0059 | 22 | | GA | | 44-0 | 29-32-11 | D03546 | | 13 | | D41058P | 24 | | | 115-199 |
| 0060 | 24 | | GK | | 41-0 | 29-33-11 | D03546 | | 15 | | D40608P | 3 | | | ALL |
| 0061 | 22 | | GA | | 7-0 | 33-16-32 | D03540 | | 3 | | TB0114Z | 15 | BJ | | 001-099 |
| 0061 | 22 | | GA | | 6-0 | 33-16-32 | D03540 | | 3 | | TB0114Z | 15 | BJ | | 115-199 |
| 0062 | 22 | | GA | | 7-0 | 33-16-42 | D03540 | | 4 | | TB0114Z | 18 | BJ | | 001-099 |
| 0062 | 22 | | GA | | 6-0 | 33-16-42 | D03540 | | 4 | | TB0114Z | 18 | BJ | | 115-199 |
| 0063 | 20 | | GA | | 7-0 | 33-13-32 | D03540 | | 1 | | TB0116Z | 22 | BJ | | 001-099 |
| 0063 | 20 | | GA | | 9-0 | 33-13-32 | D03540 | | 1 | | TB0115Z | 13 | BJ | | 115-199 |
| 0064 | 20 | | GA | | 9-0 | 33-13-32 | D03540 | | 2 | | TB0115Z | 14 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0065 | 20 | | GA | | 8-0 | 52-51-11 | D03532 | | 8 | | TB0116X | C011 | BJ | | ALL |
| 0066 | 20 | | GA | | 7-0 | 52-51-11 | D03532 | | 9 | | GD00606 | DC.. | 2 | | ALL |
| 0067 | 22 | | GA | | 46-0 | 52-51-11 | D03532 | | 12 | | D41470P | 33 | | | 001-099 |
| 0067 | 22 | | GA | | 47-0 | 52-51-11 | D03532 | | 12 | | D41470P | 33 | | | 115-199 |
| 0068 | 20 | | GA | | 12-0 | 52-51-11 | D03532 | | 7 | | D41106J | 1 | | | 001-099 |
| 0068 | 20 | | GA | | 13-0 | 52-51-11 | D03532 | | 7 | | D41106J | 1 | | | 115-199 |
| 0069 | 20 | | GA | | 2-0 | 52-51-11 | D41106J | | 2 | | GD00043 | DC.. | E | | 001-099 |
| 0069 | 20 | | GA | | 3-0 | 52-51-11 | D41106J | | 2 | | GD00043 | DC.. | E | | 115-199 |
| 0070 | 20 | | GA | | 29-0 | 36-11-21 | D03540 | | 11 | | TB0058X | A010 | BJ | | ALL |
| 0071 | 20 | | GA | | 35-0 | 36-11-21 | D41856P | | 33 | | TB0058X | B010 | BJ | | 001-099 |
| 0071 | 20 | | GA | | 36-0 | 36-11-21 | D41856P | | 33 | | TB0058X | B010 | BJ | | 115-199 |
| 0072 | 24 | | GK | | 39-0 | 36-11-22 | D03540 | | 6 | | D41860P | 2 | | | ALL |
| 0079 | 24 | | GK | | 38-0 | 33-42-12 | D41470P | | 3 | | D41172J | 14 | | | 001-099 |
| 0079 | 20 | | GA | | 39-0 | 33-42-12 | D41470P | | 3 | | D41172J | 14 | | | 115-199 |
| 0080 | 24 | | GK | | 30-0 | 33-42-11 | D41470P | | 4 | | D41412P | 3 | | | 001-099 |
| 0080 | 20 | | GA | | 29-0 | 33-42-11 | D41470P | | 4 | | D41412P | 3 | | | 115-199 |
| 0081 | 24 | | GK | | 30-0 | 33-42-11 | D41470P | | 5 | | D41412P | 2 | | | 001-099 |
| 0081 | 20 | | GA | | 29-0 | 33-42-11 | D41470P | | 5 | | D41412P | 2 | | | 115-199 |
| 0082 | 24 | | GK | | 30-0 | 33-42-11 | D41470P | | 6 | | D41412P | 1 | | | 001-099 |
| 0082 | 20 | | GA | | 29-0 | 33-42-11 | D41470P | | 6 | | D41412P | 1 | | | 115-199 |
| 0086 | 24 | | GK | | 49-0 | SPARE | D03536 | | 38 | | D41876P | 5 | | | 115-199 |
| 0087 | 24 | | GK | | 16-0 | 30-32-11 | D03704 | | 24 | | TB0113Y | A006 | BJ | | ALL |
| 0088 | 24 | | GK | | 13-0 | 29-33-11 | D40608P | | 2 | | D41058P | 28 | | | 001-099 |
| 0088 | 24 | | GK | | 12-0 | 29-33-11 | D40608P | | 2 | | D41058P | 28 | | | 115-199 |
| 0089 | 20 | | GA | | 6-0 | 33-13-32 | D03414 | | 7 | | GD00602 | ST.. | 2 | | ALL |
| 0090 | 20 | | GA | | 30-0 | SPARE | D41470P | | 21 | | D41412P | 5 | | | 001-099 |
| 0090 | 20 | | GA | | 29-0 | SPARE | D41470P | | 21 | | D41412P | 5 | | | 115-199 |
| 0091 | 24 | | GK | | 46-0 | 24-41-12 | D41470P | | 8 | | D03502 | 20 | | | 001-099 |
| 0091 | 24 | | GK | | 47-0 | 24-41-12 | D41470P | | 8 | | D03502 | 20 | | | 115-199 |
| 0092 | 20 | | GA | | 5-0 | SPARE | D03710 | | 6 | | GD00617 | DC.. | 2 | | 115-199 |
| 0093 | 24 | | GK | | 42-0 | 21-31-21 | SP00085 | | | 9 | D40598P | 3 | | | 115-199 |
| 0094 | 22 | | GA | | 25-0 | SPARE | D41856P | | 46 | | D41876P | 26 | | | 115-199 |
| 0096 | 20 | | GA | | 26-0 | SPARE | D40592P | | 14 | | D41412P | 14 | | | 001-099 |
| 0096 | 20 | | GA | | 24-0 | SPARE | D40592P | | 14 | | D41412P | 14 | | | 115-199 |
| 0097 | 16 | | GA | | 26-0 | 29-11-12 | D40592P | | 9 | 16 | D41412P | 15 | 16 | | 001-099 |
| 0097 | 16 | | GA | | 24-0 | 29-11-12 | D40592P | | 9 | 16 | D41412P | 15 | 16 | | 115-199 |
| 0098 | 16 | | GA | | 33-0 | 29-11-12 | SM00014 | | | 9 | D41412P | 12 | 16 | | 001-099 |
| 0098 | 16 | | GA | | 30-0 | 29-11-12 | SM00014 | | | 9 | D41412P | 12 | 16 | | 115-199 |
| 0099 | 20 | | GA | | 6-0 | 21-45-11 | D03094 | | 3 | | GD01252 | AC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0099 | 20 | | GA | | 7-0 | 21-45-11 | D03094 | | 3 | | GD01252 | AC.. | 2 | | 115-199 |
| 0100 | 24 | | GK | | 1-0 | 33-13-32 | D03408 | | 12 | | SM00007 | | 9 | | ALL |
| 0101 | 18 | | GA | | 9-0 | 30-42-11 | D03520 | | 7 | | D40802J | | 21 | | ALL |
| 0102 | 22 | | GA | | 29-0 | 23-51-21 | TB0113A | C009 | 2 | | TB0058Y | A005 | BJ | | 001-099 |
| 0102 | 22 | | GA | | 26-0 | 23-51-21 | D40802J | | 9 | | TB0058Y | A005 | BJ | | 115-199 |
| 0103 | 24 | | GK | | 29-0 | 33-24-11 | D40590P | | 1 | | D41470P | | 1 | | 001-099 |
| 0103 | 22 | | GA | | 29-0 | 33-24-11 | D40590P | | 1 | | D41470P | | 1 | | 115-199 |
| 0104 | 24 | | GK | | 38-0 | SPARE | D03710 | CAP | Y | | D40598P | | 30 | | 001-099 |
| 0104 | 24 | | GK | | 38-0 | SPARE | D03710 | | 5 | | D40598P | | 30 | | 115-199 |
| 0105 | 22 | | GA | | 45-0 | 24-22-21 | D03502 | | 10 | | D40598P | | 9 | | ALL |
| 0106 | 22 | | GA | | 45-0 | 24-22-21 | D03502 | | 11 | | D40598P | | 10 | | ALL |
| 0107 | 20 | | GA | | 45-0 | 24-41-11 | D03502 | | 26 | | D40590P | | 35 | | 001-099 |
| 0107 | 20 | | GA | | 46-0 | 24-41-11 | D03502 | | 26 | | D40590P | | 35 | | 115-199 |
| 0108 | 20 | | GA | | 45-0 | 24-41-11 | D03502 | | 27 | | D40590P | | 36 | | 001-099 |
| 0108 | 20 | | GA | | 46-0 | 24-41-11 | D03502 | | 27 | | D40590P | | 36 | | 115-199 |
| 0109 | 22 | | GA | | 30-0 | 24-22-21 | D03502 | | 9 | | TB0058X | C009 | BJ | | 001-099 |
| 0109 | 22 | | GA | | 31-0 | 24-22-21 | D03502 | | 9 | | TB0058X | C009 | BJ | | 115-199 |
| 0110 | 22 | | GA | | 41-0 | 24-22-21 | D40598P | | 13 | | TB0058X | D009 | BJ | | 001-099 |
| 0110 | 22 | | GA | | 42-0 | 24-22-21 | D40598P | | 13 | | TB0058X | D009 | BJ | | 115-199 |
| 0111 | 22 | | GA | | 26-0 | 27-51-21 | D41412P | | 20 | | D41172J | | 18 | | 001-099 |
| 0111 | 22 | | GA | | 22-0 | 27-51-21 | D41412P | | 20 | | D41172J | | 18 | | 115-199 |
| 0112 | 22 | | GA | | 33-0 | 29-11-12 | D03546 | | 5 | | D41412P | | 13 | | 001-099 |
| 0112 | 22 | | GA | | 30-0 | 29-11-12 | D03546 | | 5 | | D41412P | | 13 | | 115-199 |
| 0113 | 22 | | GA | | 1-0 | 29-11-12 | D03546 | | 6 | | SM00014 | | 9 | | ALL |
| 0114 | 22 | | GA | | 39-0 | SPARE | D03546 | CAP | Y | | D41856P | | 50 | | ALL |
| 0116 | 20 | | GA | | 6-0 | 33-13-32 | D03414 | | 11 | | GD00602 | AC.. | 2 | | ALL |
| 0117 | 22 | | GA | | 45-0 | 33-51-11 | D41470P | | 18 | | TB0113Z | 14 | BJ | | 001-099 |
| 0117 | 22 | | GA | | 46-0 | 33-51-11 | D41470P | | 18 | | TB0113Z | 14 | BJ | | 115-199 |
| 0118 | 22 | | GA | | 45-0 | 33-51-11 | D41470P | | 20 | | D04800 | | 2 | | 001-099 |
| 0118 | 22 | | GA | | 46-0 | 33-51-11 | D41470P | | 20 | | D04800 | | 2 | | 115-199 |
| 0119 | 24 | | GK | | 20-0 | 36-11-31 | D40970P | | 5 | | D41856P | | 2 | | 001-099 |
| 0119 | 24 | | GK | | 21-0 | 36-11-31 | D40970P | | 5 | | D41856P | | 2 | | 115-199 |
| 0120 | 24 | | GK | | 41-0 | 24-27-21 | D03502 | | 36 | | D40592P | | 17 | | 001-099 |
| 0120 | 24 | | GK | | 43-0 | 24-27-21 | D03502 | | 36 | | D40592P | | 17 | | 115-199 |
| 0121 | 22 | | GA | | 26-0 | 27-51-21 | D41172J | | 20 | | D41412P | | 6 | | 001-099 |
| 0121 | 22 | | GA | | 22-0 | 27-51-21 | D41172J | | 20 | | D41412P | | 6 | | 115-199 |
| 0122 | 20 | | GA | | 9-0 | 33-13-32 | D03414 | | 2 | | TB0115Z | 7 | BJ | | ALL |
| 0123 | 22 | | GA | | 17-0 | 33-16-41 | D41006P | | 2 | | D41172J | | 19 | | 001-099 |
| 0123 | 22 | | GA | | 16-0 | 33-16-41 | D41006P | | 2 | | D41172J | | 19 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | |
| 0124 | 22 | GA | | 27-0 | SPARE | D41058P | 34 | | | D41470P | CAP | Y | | 115-199 |
| 0125 | 24 | GK | | 25-0 | SPARE | D40608P | 1 | | | D41412P | 4 | | | 001-099 |
| 0125 | 24 | GK | | 22-0 | SPARE | D40608P | 1 | | | D41412P | 4 | | | 115-199 |
| 0126 | 20 | GA | | 4-0 | 33-13-32 | D03408 | 2 | | | TB0116Z | 22 | BJ | | 001-099 |
| 0126 | 20 | GA | | 9-0 | 33-13-32 | D03408 | 2 | | | TB0115Z | 13 | BJ | | 115-199 |
| 0127 | 24 | GK | | 3-0 | 33-13-32 | D03414 | 12 | | | SM00007 | 9 | | | 001-099 |
| 0127 | 24 | GK | | 2-0 | 33-13-32 | D03414 | 12 | | | SM00007 | 9 | | | 115-199 |
| 0128 | 22 | GA | | 17-0 | 24-22-21 | D03502 | 23 | | | D03710 | 11 | | | 001-003, 115-199 |
| 0129 | 20 | GA | | 6-0 | 33-13-32 | D03408 | 11 | | | GD00602 | AC.. | 2 | | ALL |
| 0130 | 20 | GA | | 6-0 | 33-13-32 | D03408 | 7 | | | GD00602 | ST.. | 2 | | ALL |
| 0131 | 20 | GA | | 17-0 | 33-41-11 | D41856P | 54 | | | D40608P | 35 | | | ALL |
| 0132 | 24 | GK | | 45-0 | 24-27-21 | D03502 | 34 | | | D41058P | 21 | | | 001-099 |
| 0132 | 24 | GK | | 44-0 | 24-27-21 | D03502 | 34 | | | D41058P | 21 | | | 115-199 |
| 0133 | 24 | GK | | 33-0 | 36-11-21 | D03540 | 9 | | | D40970P | 32 | | | 001-099 |
| 0133 | 24 | GK | | 38-0 | 36-11-21 | D03540 | 9 | | | D41856P | 34 | | | 115-199 |
| 0134 | 20 | GA | | 38-0 | 36-11-21 | D03540 | 10 | | | D41856P | 35 | | | ALL |
| 0135 | 20 | GA | | 20-0 | 36-11-21 | D41856P | 36 | | | D40970P | 39 | | | 001-099 |
| 0135 | 20 | GA | | 21-0 | 36-11-21 | D41856P | 36 | | | D40970P | 39 | | | 115-199 |
| 0136 | 24 | GK | | 20-0 | 36-11-21 | D41856P | 37 | | | D40970P | 21 | | | 001-099 |
| 0136 | 24 | GK | | 21-0 | 36-11-21 | D41856P | 37 | | | D40970P | 21 | | | 115-199 |
| 0137 | 24 | GK | | 25-0 | 36-11-21 | D40970P | 33 | | | D41058P | 17 | | | 001-099 |
| 0137 | 24 | GK | | 20-0 | 36-11-21 | D41856P | 38 | | | D41058P | 17 | | | 115-199 |
| 0138 | 24 | GK | | 45-0 | 24-27-21 | D03502 | 35 | | | D41058P | 1 | | | 001-099 |
| 0138 | 24 | GK | | 44-0 | 24-27-21 | D03502 | 35 | | | D41058P | 1 | | | 115-199 |
| 0139 | 24 | GK | | 45-0 | 24-27-21 | D03502 | 15 | | | D41058P | 2 | | | 001-099 |
| 0139 | 24 | GK | | 44-0 | 24-27-21 | D03502 | 15 | | | D41058P | 2 | | | 115-199 |
| 0140 | 20 | GA | | 5-0 | 24-51-24 | D03502 | 19 | | | TB0113X | C016 | BJ | | ALL |
| 0141 | 20 | GA | | 39-0 | 24-51-24 | D03502 | 8 | | | D41856P | 31 | | | ALL |
| 0142 | 22 | GA | | 39-0 | 24-51-24 | D03502 | 5 | | | D41856P | 40 | | | ALL |
| 0143 | 22 | GA | | 45-0 | 24-51-24 | D03502 | 16 | | | D41058P | 4 | | | 001-099 |
| 0143 | 22 | GA | | 44-0 | 24-51-24 | D03502 | 16 | | | D41058P | 4 | | | 115-199 |
| 0144 | 24 | GK | | 39-0 | 36-22-11 | D03540 | 12 | | | D42176P | 7 | | | 001-099 |
| 0144 | 24 | GK | | 42-0 | 36-22-11 | D03540 | 12 | | | D41058P | 5 | | | 115-199 |
| 0145 | 24 | GK | | 16-0 | SPARE | D40598P | 45 | | | D41058P | 6 | | | 115-199 |
| 0146 | 24 | GK | | 23-0 | 29-33-11 | D40608P | 30 | | | D41876P | 31 | | | 001-099 |
| 0146 | 24 | GK | | 22-0 | SPARE | D40608P | 30 | | | D40970P | 12 | | | 115-199 |
| 0147 | 20 | GA | | 29-0 | 21-45-11 | SM00001 | | 9 | | D41856P | 5 | | | 001-099 |
| 0147 | 20 | GA | | 28-0 | 21-45-11 | SM00001 | | 9 | | D41856P | 5 | | | 115-199 |
| 0148 | 20 | GA | | 32-0 | 21-45-11 | D03094 | 7 | | | D41856P | 6 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0149 | 20 | | GA | | 32-0 | 21-45-11 | D03094 | | 8 | | D41856P | | 7 | | ALL |
| 0151 | 24 | | GK | | 7-0 | 21-25-11 | D03558 | | 25 | | TB0113Y | A003 | BJ | | 001-099 |
| 0151 | 24 | | GK | | 6-0 | 21-25-11 | D03558 | | 25 | | TB0113Y | A003 | BJ | | 115-199 |
| 0154 | 24 | | GK | | 38-0 | 21-25-11 | D03558 | | 24 | | D41856P | | 30 | | 001-099 |
| 0154 | 24 | | GK | | 37-0 | 21-25-11 | D03558 | | 24 | | D41856P | | 30 | | 115-199 |
| 0156 | 24 | | GK | | 44-0 | 21-25-11 | TB0113Y | A003 | BJ | | D41058P | | 7 | | 001-099 |
| 0156 | 24 | | GK | | 43-0 | 21-25-11 | TB0113Y | A003 | BJ | | D41058P | | 7 | | 115-199 |
| 0157 | 22 | | GA | | 30-0 | 28-21-21 | D40970P | | 13 | | D41876P | | 1 | | 001-099 |
| 0157 | 22 | | GA | | 31-0 | 28-21-21 | D40970P | | 13 | | D41876P | | 1 | | 115-199 |
| 0158 | 20 | | GA | | 8-0 | 33-13-31 | D03520 | | 1 | | TB0114Z | 11 | BJ | | 001-099 |
| 0158 | 20 | | GA | | 7-0 | 33-13-31 | D03520 | | 1 | | TB0114Z | 11 | BJ | | 115-199 |
| 0159 | 20 | | GA | | 8-0 | 33-13-31 | D03520 | | 2 | | TB0114Z | 12 | BJ | | 001-099 |
| 0159 | 20 | | GA | | 7-0 | 33-13-31 | D03520 | | 2 | | TB0114Z | 12 | BJ | | 115-199 |
| 0160 | 24 | | GK | | 33-0 | 33-24-11 | D41470P | | 2 | | D41876P | | 3 | | 001-099 |
| 0160 | 22 | | GA | | 33-0 | 33-24-11 | D41470P | | 2 | | D41876P | | 3 | | 115-199 |
| 0166 | 20 | | GA | | 49-0 | 28-41-11 | D06870 | | 12 | | D41876P | | 16 | | ALL |
| 0167 | 24 | | GK | | 24-0 | 34-61-21 | D40802J | | 27 | | TB0100X | D004 | BJ | | ALL |
| 0168 | 22 | | GA | | 44-0 | 29-11-12 | TB0113A | C022 | 2 | | D41058P | | 8 | | 001-099 |
| 0168 | 22 | | GA | | 43-0 | 29-11-12 | TB0113A | C022 | 2 | | D41058P | | 8 | | 115-199 |
| 0169 | 22 | | GA | | 45-0 | 29-11-12 | D03546 | | 24 | | D41058P | | 27 | | 001-099 |
| 0169 | 22 | | GA | | 44-0 | 29-11-12 | D03546 | | 24 | | D41058P | | 27 | | 115-199 |
| 0170 | 22 | | GA | | 45-0 | 29-11-12 | D03546 | | 25 | | D41058P | | 26 | | 001-099 |
| 0170 | 22 | | GA | | 44-0 | 29-11-12 | D03546 | | 25 | | D41058P | | 26 | | 115-199 |
| 0172 | 22 | | GA | | 30-0 | 29-11-21 | D03546 | | 12 | | TB0059X | B007 | BJ | | ALL |
| 0173 | 22 | | GA | | 30-0 | 29-11-21 | D03546 | | 10 | | TB0059X | C007 | BJ | | ALL |
| 0174 | 22 | | GA | | 30-0 | 29-11-21 | D03546 | | 11 | | TB0059X | D007 | BJ | | ALL |
| 0177 | 20 | | GA | | 9-0 | 25-31-11 | D03502 | | 17 | | D40802J | | 26 | | 001-099 |
| 0177 | 20 | | GA | | 8-0 | 25-31-21 | TB0114X | A013 | BJ | | D03502 | | 17 | | 115-199 |
| 0178 | 22 | | GA | | 9-0 | SPARE | D41856P | | 55 | | D40592P | | 6 | | 001-099 |
| 0178 | 22 | | GA | | 10-0 | SPARE | D41856P | | 55 | | D40592P | | 6 | | 115-199 |
| 0179 | 22 | | GA | | 1-0 | 29-11-31 | D03546 | | 2 | | SM00015 | | 9 | | ALL |
| 0180 | 24 | | GK | | 32-0 | 21-51-13 | D03558 | | 13 | | D40970P | | 1 | | 001-099 |
| 0180 | 24 | | GK | | 31-0 | 21-51-13 | D03558 | | 13 | | D40970P | | 1 | | 115-199 |
| 0181 | 24 | | GK | | 32-0 | 21-51-13 | D03558 | | 12 | | D40970P | | 2 | | 001-099 |
| 0181 | 24 | | GK | | 31-0 | 21-51-13 | D03558 | | 12 | | D40970P | | 2 | | 115-199 |
| 0182 | 24 | | GK | | 32-0 | 21-51-13 | D03558 | | 11 | | D40970P | | 3 | | 001-099 |
| 0182 | 24 | | GK | | 31-0 | 21-51-13 | D03558 | | 11 | | D40970P | | 3 | | 115-199 |
| 0183 | 24 | | GK | | 32-0 | 21-51-13 | D03558 | | 10 | | D40970P | | 4 | | 001-099 |
| 0183 | 24 | | GK | | 31-0 | 21-51-13 | D03558 | | 10 | | D40970P | | 4 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0184 | 22 | | GA | 5-0 | 21-51-13 | D03558 | 14 | | | | GD00606 | DC.. | 2 | | ALL |
| 0185 | 24 | | GK | 32-0 | 21-51-21 | D03558 | 8 | | | | D40970P | 10 | | | 001-099 |
| 0185 | 24 | | GK | 31-0 | 21-51-21 | D03558 | 8 | | | | D40970P | 10 | | | 115-199 |
| 0186 | 22 | | GA | 5-0 | 21-51-21 | D03558 | 9 | | | | GD00606 | DC.. | 2 | | ALL |
| 0187 | 24 | | GK | 7-0 | 21-51-22 | D03558 | 7 | | | | TB0113X | B016 | BJ | | 001-099 |
| 0187 | 24 | | GK | 6-0 | 21-51-22 | D03558 | 7 | | | | TB0113X | B016 | BJ | | 115-199 |
| 0188 | 24 | | GK | 38-0 | 21-51-22 | D03558 | 6 | | | | D41856P | 9 | | | 001-099 |
| 0188 | 24 | | GK | 37-0 | 21-51-22 | D03558 | 6 | | | | D41856P | 9 | | | 115-199 |
| 0189 | 24 | | GK | 32-0 | 21-51-25 | D03558 | 27 | | | | D40970P | 14 | | | 001-099 |
| 0189 | 24 | | GK | 31-0 | 21-51-25 | D03558 | 27 | | | | D40970P | 14 | | | 115-199 |
| 0190 | 24 | | GK | 5-0 | 21-51-25 | D03558 | 28 | | | | GD00606 | DC.. | 2 | | ALL |
| 0191 | 24 | | GK | 32-0 | 21-51-25 | D03558 | 29 | | | | D40970P | 15 | | | 001-099 |
| 0191 | 24 | | GK | 31-0 | 21-51-25 | D03558 | 29 | | | | D40970P | 15 | | | 115-199 |
| 0192 | 24 | | GK | 32-0 | 21-51-25 | D03558 | 30 | | | | D40970P | 16 | | | 001-099 |
| 0192 | 24 | | GK | 31-0 | 21-51-25 | D03558 | 30 | | | | D40970P | 16 | | | 115-199 |
| 0193 | 24 | | GK | 25-0 | 21-51-25 | D41058P | 10 | | | | D40970P | 17 | | | ALL |
| 0194 | 24 | | GK | 25-0 | 21-51-25 | D41058P | 9 | | | | D40970P | 18 | | | ALL |
| 0195 | 24 | | GK | 5-0 | 21-61-11 | D03558 | 33 | | | | GD00606 | DC.. | 2 | | ALL |
| 0196 | 24 | | GK | 5-0 | 21-61-11 | D03558 | 32 | | | | GD00606 | ST.. | 2 | | ALL |
| 0197 | 20 | | GA | 7-0 | 33-13-32 | TB0115Z | 14 | BJ | | | GD00602 | AC.. | 2 | | ALL |
| 0200 | 20 | | GA | 5-0 | 33-13-21 | D03094 | 1 | | | | D41172J | 1 | | | ALL |
| 0201 | 20 | | GA | 6-0 | 33-13-21 | D03094 | 2 | | | | GD01252 | AC.. | 2 | | 001-099 |
| 0201 | 20 | | GA | 7-0 | 33-13-21 | D03094 | 2 | | | | GD01252 | AC.. | 2 | | 115-199 |
| 0202 | 16 | | GA | 19-0 | 29-11-31 | D40592P | 15 | 16 | | | D40608P | 23 | | | 001-099 |
| 0202 | 16 | | GA | 20-0 | 29-11-31 | D40592P | 15 | 16 | | | D40608P | 5 | 16 | | 115-199 |
| 0203 | 22 | | GA | 19-0 | 29-11-31 | D40592P | 16 | | | | D40608P | 6 | | | 001-099 |
| 0203 | 22 | | GA | 20-0 | 29-11-31 | D40592P | 16 | | | | D40608P | 6 | | | 115-199 |
| 0204 | 24 | | GK | 38-0 | 21-61-11 | D03558 | 38 | | | | D41856P | 13 | | | 001-099 |
| 0204 | 24 | | GK | 37-0 | 21-61-11 | D03558 | 38 | | | | D41856P | 13 | | | 115-199 |
| 0205 | 24 | | GK | 38-0 | 21-61-11 | D03558 | 34 | | | | D41856P | 14 | | | 001-099 |
| 0205 | 24 | | GK | 37-0 | 21-61-11 | D03558 | 34 | | | | D41856P | 14 | | | 115-199 |
| 0206 | 24 | | GK | 38-0 | 21-61-21 | D03558 | 45 | | | | D41856P | 15 | | | 001-099 |
| 0206 | 24 | | GK | 37-0 | 21-61-21 | D03558 | 45 | | | | D41856P | 15 | | | 115-199 |
| 0207 | 24 | | GK | 5-0 | 21-61-21 | D03558 | 40 | | | | GD00606 | DC.. | 2 | | ALL |
| 0208 | 24 | | GK | 38-0 | 21-61-21 | D03558 | 41 | | | | D41856P | 16 | | | 001-099 |
| 0208 | 24 | | GK | 37-0 | 21-61-21 | D03558 | 41 | | | | D41856P | 16 | | | 115-199 |
| 0209 | 22 | | GA | 41-0 | 29-11-31 | D03546 | 1 | | | | D40592P | 1 | | | 001-099 |
| 0209 | 22 | | GA | 43-0 | 29-11-31 | D03546 | 1 | | | | D40592P | 1 | | | 115-199 |
| 0210 | 20 | | GA | 24-0 | 33-43-11 | D41856P | 32 | | | | D41412P | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2070 | 286N2070 | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | | | |
| 0210 | 20 | GA | 21-0 | 33-43-11 | D41856P | 32 | | | D41412P | 18 | | | 115-199 | | |
| 0211 | 16 | GA | 40-0 | 29-11-31 | D40608P | 21 | | | SM00015 | | 9 | | 001-099 | | |
| 0211 | 16 | GA | 40-0 | 29-11-31 | D40608P | 4 | 16 | | SM00015 | | 9 | | 115-199 | | |
| 0212 | 24 | GK | 5-0 | 21-61-21 | D03558 | 39 | | | GD00606 | ST.. | 2 | | ALL | | |
| 0214 | 24 | GK | 3-0 | 33-11-11 | D41004P | 19 | | | TB0121X | D006 | BJ | | ALL | | |
| 0216 | 24 | GK | 22-0 | 21-61-21 | D41058P | 11 | | | D41856P | 20 | | | 001-099 | | |
| 0216 | 24 | GK | 20-0 | 21-61-21 | D41058P | 11 | | | D41856P | 20 | | | 115-199 | | |
| 0217 | 24 | GK | 45-0 | 24-22-22 | D03502 | 32 | | | D40598P | 17 | | | ALL | | |
| 0218 | 20 | GA | 41-0 | 24-22-22 | D03502 | 33 | | | D40592P | 4 | | | 001-099 | | |
| 0218 | 20 | GA | 43-0 | 24-22-22 | D03502 | 33 | | | D40592P | 4 | | | 115-199 | | |
| 0219 | 22 | GA | 13-0 | 33-16-31 | TB0113X | A012 | BJ | | D41004P | 1 | | | ALL | | |
| 0220 | 24 | GK | 36-0 | 33-11-31 | D41470P | 22 | | | D41004P | 12 | | | 001-099 | | |
| 0220 | 24 | GK | 38-0 | 33-11-31 | D41470P | 22 | | | D41004P | 12 | | | 115-199 | | |
| 0222 | 20 | GA | 7-0 | 33-13-32 | D03558 | 1 | | | TB0116Z | 22 | BJ | | 001-099 | | |
| 0222 | 20 | GA | 8-0 | 33-13-32 | D03558 | 1 | | | TB0115Z | 13 | BJ | | 115-199 | | |
| 0223 | 20 | GA | 8-0 | 33-13-32 | D03558 | 2 | | | TB0115Z | 14 | BJ | | ALL | | |
| 0224 | 24 | GK | 9-0 | 33-13-71 | D02896 | 12 | | | TB0114Y | C005 | BJ | | 115-199 | | |
| 0225 | 24 | GK | 45-0 | 24-11-21 | D03502 | 28 | | | D40598P | 39 | | | ALL | | |
| 0229 | 22 | GA | 13-0 | 33-16-32 | D41004P | 8 | | | TB0113X | B012 | BJ | | ALL | | |
| 0230 | 22 | GA | 12-0 | 33-16-32 | D41004P | 4 | | | TB0114Z | 15 | BJ | | ALL | | |
| 0231 | 22 | GA | 35-0 | 78-34-21 | D40802J | 22 | | | D41860P | 30 | | | 001-002, 115-199 | | |
| 0231 | 22 | GA | 35-0 | 78-34-21 | D40802J | 22 | | | D42176P | 19 | | | 003-099 | | |
| 0234 | 22 | GA | 8-0 | 33-16-52 | D03502 | 3 | | | TB0116X | B016 | BJ | | ALL | | |
| 0235 | 22 | GA | 8-0 | 33-16-52 | D03502 | 21 | | | TB0116X | A016 | BJ | | ALL | | |
| 0237 | 22 | GA | 7-0 | 30-43-11 | TB0113X | B011 | BJ | | D03520 | 8 | | | 001-099 | | |
| 0237 | 22 | GA | 6-0 | 30-43-11 | TB0113X | B011 | BJ | | D03520 | 8 | | | 115-199 | | |
| 0238 | 22 | GA | 8-0 | 30-43-11 | D03520 | 9 | | | TB0115X | D002 | BJ | | ALL | | |
| 0239 | 22 | GA | 24-0 | 30-43-11 | D41172J | 17 | | | TB0114X | C014 | BJ | | ALL | | |
| 0240 | 20 | GA | 9-0 | 23-11-21 | D40802J | 28 | | | TB0113X | C001 | BJ | | ALL | | |
| 0241 | 22 | GA | 25-0 | 34-53-21 | D40802J | 29 | | | TB0058Y | C013 | BJ | | 001-099 | | |
| 0241 | 22 | GA | 26-0 | 34-53-21 | D40802J | 29 | | | TB0058Y | C013 | BJ | | 115-199 | | |
| 0242 | 22 | GA | 39-0 | 27-32-11 | D40590P | 5 | | | D03704 | 16 | | | ALL | | |
| 0243 | 20 | GA | 15-0 | 27-32-11 | D03704 | 17 | | | GD00611 | DC.. | 2 | | ALL | | |
| 0244 | 22 | GA | 9-0 | 31-51-12 | D40802J | 30 | | | TB0113X | C011 | BJ | | ALL | | |
| 0245 | 20 | GA | 28-0 | 23-31-11 | D41470P | 7 | | | D41058P | 29 | | | 001-099 | | |
| 0245 | 20 | GA | 27-0 | 23-31-11 | D41470P | 7 | | | D41058P | 29 | | | 115-199 | | |
| 0246 | 22 | GA | 9-0 | 22-21-21 | D40802J | 7 | | | TB0113X | D016 | BJ | | ALL | | |
| 0255 | 22 | GA | 18-0 | 33-51-11 | D40356P | 4 | | | TB0113Z | 14 | BJ | | 001-099 | | |
| 0255 | 22 | GA | 20-0 | 33-51-11 | D40356P | 4 | | | TB0113Z | 14 | BJ | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0256 | 22 | GA | | | 18-0 | 33-51-11 | D40356P | 3 | | | D04800 | 6 | | | 001-099 |
| 0256 | 22 | GA | | | 20-0 | 33-51-11 | D40356P | 3 | | | D04800 | 6 | | | 115-199 |
| 0257 | 22 | GA | | | 18-0 | 33-51-11 | D40354P | 3 | | | D04800 | 15 | | | 001-099 |
| 0257 | 22 | GA | | | 20-0 | 33-51-11 | D40354P | 3 | | | D04800 | 15 | | | 115-199 |
| 0258 | 22 | GA | | | 18-0 | 33-51-11 | D40354P | 4 | | | TB0113Z | 14 | BJ | | 001-099 |
| 0258 | 22 | GA | | | 20-0 | 33-51-11 | D40354P | 4 | | | TB0113Z | 14 | BJ | | 115-199 |
| 0261 | 22 | GA | | | 29-0 | SPARE | D40590P | 29 | | | D41470P | 29 | | | ALL |
| 0262 | 24 | GK | | | 38-0 | 21-61-31 | D03558 | 21 | | | D41856P | 41 | | | 001-099 |
| 0262 | 24 | GK | | | 37-0 | 21-61-31 | D03558 | 21 | | | D41856P | 41 | | | 115-199 |
| 0263 | 24 | GK | | | 5-0 | 21-61-31 | D03558 | 16 | | | GD00606 | DC.. | 2 | | ALL |
| 0264 | 24 | GK | | | 38-0 | 21-61-31 | D03558 | 17 | | | D41856P | 21 | | | 001-099 |
| 0264 | 24 | GK | | | 37-0 | 21-61-31 | D03558 | 17 | | | D41856P | 21 | | | 115-199 |
| 0265 | 24 | GK | | | 5-0 | 21-61-31 | D03558 | 15 | | | GD00606 | ST.. | 2 | | ALL |
| 0266 | 24 | GK | | | 22-0 | 21-61-31 | D41058P | 23 | | | D41856P | 22 | | | 001-099 |
| 0266 | 24 | GK | | | 20-0 | 21-61-31 | D41058P | 23 | | | D41856P | 22 | | | 115-199 |
| 0270 | 22 | GA | | | 17-0 | 33-16-31 | D41172J | 27 | | | D41004P | 7 | | | 001-099 |
| 0270 | 22 | GA | | | 16-0 | 33-16-31 | D41172J | 27 | | | D41004P | 7 | | | 115-199 |
| 0271 | 22 | GA | | | 44-0 | 28-42-11 | D03514 | 11 | | | D41058P | 12 | | | 001-099 |
| 0271 | 22 | GA | | | 43-0 | 28-42-11 | D03514 | 11 | | | D41058P | 12 | | | 115-199 |
| 0272 | 22 | GA | | | 10-10 | 28-42-11 | D03514 | 25 | | | SM00033 | | 9 | | ALL |
| 0273 | 22 | GA | | | 44-0 | 28-42-11 | D03514 | 21 | | | D41058P | 14 | | | 001-099 |
| 0273 | 22 | GA | | | 43-0 | 28-42-11 | D03514 | 21 | | | D41058P | 14 | | | 115-199 |
| 0274 | 22 | GA | | | 44-0 | 28-42-11 | D03514 | 5 | | | D41058P | 15 | | | 001-099 |
| 0274 | 22 | GA | | | 43-0 | 28-42-11 | D03514 | 5 | | | D41058P | 15 | | | 115-199 |
| 0275 | 22 | GA | | | 7-0 | 33-16-13 | D03710 | 4 | | | TB0121Z | 15 | BJ | | 001-003 |
| 0275 | 22 | GA | | | 6-0 | 33-16-13 | D03710 | 4 | | | TB0121Z | 15 | BJ | | 115-199 |
| 0276 | 24 | GK | | | 8-0 | 33-16-12 | TB0113Y | C006 | BJ | | D03532 | 18 | | | 001-099 |
| 0276 | 24 | GK | | | 8-0 | 33-16-12 | SP01936 | | 9 | | D03532 | 18 | | | 115-199 |
| 0277 | 22 | GA | | | 8-0 | 33-16-12 | TB0112Z | 11 | BJ | | D03532 | 4 | | | 001-099 |
| 0277 | 22 | GA | | | 7-0 | 33-16-12 | TB0112Z | 11 | BJ | | D03532 | 4 | | | 115-199 |
| 0278 | 20 | GA | | | 7-0 | 33-16-12 | GD00611 | DC.. | 2 | | D03532 | 19 | | | ALL |
| 0280 | 22 | GA | | | 8-0 | 33-16-22 | TB0112X | A004 | BJ | | D03532 | 3 | | | 001-099 |
| 0280 | 22 | GA | | | 7-0 | 33-16-22 | TB0112X | A004 | BJ | | D03532 | 3 | | | 115-199 |
| 0281 | 22 | GA | | | 9-0 | 33-16-31 | D40802J | 17 | | | D41004P | 3 | | | ALL |
| 0282 | 22 | GA | | | 3-0 | 33-16-31 | SM00008 | | 9 | | D41004P | 6 | | | ALL |
| 0283 | 20 | GA | | | 3-0 | 33-16-31 | GD01221 | DC.. | 2 | | D41004P | 9 | | | ALL |
| 0284 | 22 | GA | | | 12-0 | 33-16-32 | TB0114Y | A003 | BJ | | D41004P | 2 | | | ALL |
| 0286 | 22 | GA | | | 7-0 | 33-16-33 | D03710 | 1 | | | SM00008 | | 9 | | 001-099 |
| 0286 | 22 | GA | | | 5-0 | 33-16-33 | D03710 | 1 | | | SM00008 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|------|--|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2070 | 286N2070 | | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | | |
| 0287 | 22 | GA | | 10-0 | 33-16-32 | SM00008 | | 9 | | | TB0114Z | 2 | BJ | | 001-099 | | |
| 0287 | 22 | GA | | 11-0 | 33-16-32 | SM00008 | | 9 | | | TB0114Z | 2 | BJ | | 115-199 | | |
| 0288 | 22 | GA | | 32-6 | 28-42-11 | D41058P | | 13 | | | SM00033 | | 9 | | ALL | | |
| 0289 | 22 | GA | | 9-0 | 33-16-41 | D41006P | | 5 | | | D40802J | | 19 | | ALL | | |
| 0290 | 20 | GA | | 3-0 | 33-16-41 | D41006P | | 1 | | | GD01221 | DC.. | 2 | | ALL | | |
| 0291 | 20 | GA | | 3-0 | 33-16-41 | D41006P | | 9 | | | GD01221 | DC.. | 2 | | ALL | | |
| 0292 | 20 | GA | | 3-0 | 33-16-41 | D41006P | | 6 | | | GD01221 | DC.. | 2 | | ALL | | |
| 0293 | 22 | GA | | 4-0 | 33-16-41 | D41006P | | 3 | | | SM00009 | | 9 | | 001-099 | | |
| 0293 | 22 | GA | | 3-0 | 33-16-41 | D41006P | | 3 | | | SM00009 | | 9 | | 115-199 | | |
| 0294 | 22 | GA | | 4-0 | 33-16-41 | D41006P | | 8 | | | SM00010 | | 9 | | 001-099 | | |
| 0294 | 22 | GA | | 3-0 | 33-16-41 | D41006P | | 8 | | | SM00010 | | 9 | | 115-199 | | |
| 0295 | 22 | GA | | 4-0 | 33-16-41 | D41006P | | 4 | | | SM00011 | | 9 | | 001-099 | | |
| 0295 | 22 | GA | | 3-0 | 33-16-41 | D41006P | | 4 | | | SM00011 | | 9 | | 115-199 | | |
| 0296 | 20 | GA | | 7-0 | 33-13-71 | D02896 | | 2 | | | TB0121Z | 9 | BJ | | 115-199 | | |
| 0297 | 22 | GA | | 4-0 | 33-16-41 | D41006P | | 7 | | | SM00012 | | 9 | | 001-099 | | |
| 0297 | 22 | GA | | 3-0 | 33-16-41 | D41006P | | 7 | | | SM00012 | | 9 | | 115-199 | | |
| 0298 | 22 | GA | | 7-0 | 33-16-43 | D03710 | | 2 | | | SM00012 | | 9 | | 001-099 | | |
| 0298 | 22 | GA | | 5-0 | 33-16-43 | D03710 | | 2 | | | SM00012 | | 9 | | 115-199 | | |
| 0299 | 22 | GA | | 7-0 | 33-16-32 | D03514 | | 3 | | | TB0114Z | 2 | BJ | | 001-099 | | |
| 0299 | 22 | GA | | 6-0 | 33-16-32 | D03514 | | 3 | | | TB0114Z | 2 | BJ | | 115-199 | | |
| 0300 | 22 | GA | | 7-0 | 33-16-42 | D03514 | | 4 | | | TB0114Z | 18 | BJ | | 001-099 | | |
| 0300 | 22 | GA | | 6-0 | 33-16-42 | D03514 | | 4 | | | TB0114Z | 18 | BJ | | 115-199 | | |
| 0301 | 22 | GA | | 8-0 | 33-16-32 | D03546 | | 3 | | | TB0114Z | 15 | BJ | | ALL | | |
| 0302 | 22 | GA | | 8-0 | 33-16-42 | D03546 | | 4 | | | TB0114Z | 18 | BJ | | ALL | | |
| 0303 | 22 | GA | | 8-0 | 33-16-32 | D03502 | | 1 | | | TB0114Z | 2 | BJ | | ALL | | |
| 0304 | 22 | GA | | 8-0 | 33-16-42 | D03502 | | 2 | | | TB0114Z | 18 | BJ | | ALL | | |
| 0305 | 22 | GA | | 6-0 | 33-16-42 | D03558 | | 4 | | | TB0114Z | 20 | BJ | | 001-099 | | |
| 0305 | 22 | GA | | 5-0 | 33-16-42 | D03558 | | 4 | | | TB0114Z | 20 | BJ | | 115-199 | | |
| 0306 | 22 | GA | | 6-0 | 33-16-42 | D03558 | | 3 | | | TB0114Z | 16 | BJ | | 001-099 | | |
| 0306 | 22 | GA | | 5-0 | 33-16-42 | D03558 | | 3 | | | TB0114Z | 16 | BJ | | 115-199 | | |
| 0307 | 22 | GA | | 6-0 | 33-16-32 | D03558 | | 5 | | | TB0114Z | 15 | BJ | | 001-099 | | |
| 0307 | 22 | GA | | 5-0 | 33-16-32 | D03558 | | 5 | | | TB0114Z | 15 | BJ | | 115-199 | | |
| 0310 | 24 | GK | | 22-0 | 21-58-13 | D41058P | | 35 | | | D41860P | 1 | | | 001-099 | | |
| 0310 | 24 | GK | | 21-0 | 21-58-13 | D41058P | | 35 | | | D41860P | 1 | | | 115-199 | | |
| 0311 | 20 | GA | | 6-0 | 33-13-71 | D02896 | | 11 | | | GD00617 | AC.. | 2 | | 115-199 | | |
| 0312 | 22 | GA | | 7-0 | 33-16-63 | D03710 | | 3 | | | TB0121X | B006 | BJ | | 001-003 | | |
| 0312 | 22 | GA | | 6-0 | 33-16-63 | D03710 | | 3 | | | TB0121X | B006 | BJ | | 115-199 | | |
| 0313 | 22 | GA | | 18-0 | 33-51-12 | TB0111X | | C002 | BJ | | D40354P | 7 | | | 001-099 | | |
| 0313 | 22 | GA | | 23-0 | 33-51-12 | D05264 | | 1 | VY | | D40354P | 7 | | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0314 | 22 | GA | | | 29-5 | 28-22-11 | D41860P | 21 | | | SM00033 | | 9 | | 001-099 |
| 0314 | 22 | GA | | | 29-9 | 28-22-11 | D41860P | 21 | | | SM00033 | | 9 | | 115-199 |
| 0315 | 22 | GA | | | 7-0 | 33-16-52 | D03502 | 4 | | | TB0115Z | 11 | BJ | | ALL |
| 0316 | 22 | GA | | | 8-0 | 33-16-62 | D03502 | 31 | | | TB0116Z | 4 | BJ | | ALL |
| 0317 | 22 | GA | | | 14-0 | 33-11-31 | D03532 | 13 | | | D41004P | 10 | | | 001-099 |
| 0317 | 22 | GA | | | 3-0 | 33-11-31 | SM00006 | | 9 | | D41004P | 10 | | | 115-199 |
| 0318 | 22 | GA | | | 14-0 | 33-11-31 | D03532 | 15 | | | D41004P | 11 | | | 001-099 |
| 0318 | 22 | GA | | | 3-0 | 33-11-31 | SM00013 | | 9 | | D41004P | 11 | | | 115-199 |
| 0319 | 22 | GA | | | 12-0 | 33-11-31 | D41004P | 13 | | | GD00611 | AC.. | 2 | | ALL |
| 0321 | 20 | GA | | | 7-0 | 33-11-31 | D03532 | 5 | | | GD00611 | AC.. | 2 | | ALL |
| 0322 | 24 | GK | | | 11-0 | 33-11-41 | TB0116X | D012 | BJ | | D41006P | 23 | | | 001-099 |
| 0322 | 24 | GK | | | 10-0 | 33-11-41 | TB0116X | D012 | BJ | | D41006P | 23 | | | 115-199 |
| 0323 | 20 | GA | | | 3-0 | 33-11-41 | GD01221 | DC.. | 2 | | D41006P | 24 | | | ALL |
| 0324 | 22 | GA | | | 10-0 | 33-16-42 | TB0114Z | 20 | BJ | | SM00010 | | 9 | | 001-099 |
| 0324 | 22 | GA | | | 11-0 | 33-16-42 | TB0114Z | 20 | BJ | | SM00010 | | 9 | | 115-199 |
| 0327 | 22 | GA | | | 10-0 | 33-16-42 | TB0114Z | 16 | BJ | | SM00011 | | 9 | | 001-099 |
| 0327 | 22 | GA | | | 11-0 | 33-16-42 | TB0114Z | 16 | BJ | | SM00011 | | 9 | | 115-199 |
| 0328 | 24 | GK | | | 17-0 | 33-11-11 | D41172J | 2 | | | D41004P | 20 | | | 001-099 |
| 0328 | 24 | GK | | | 16-0 | 33-11-11 | D41172J | 2 | | | D41004P | 20 | | | 115-199 |
| 0329 | 16 | GA | | | 9-0 | 29-11-12 | D40802J | 20 | 16 | | SM00014 | | 9 | | ALL |
| 0330 | 16 | GA | | | 9-0 | 29-11-31 | D40802J | 18 | 16 | | SM00015 | | 9 | | ALL |
| 0331 | 24 | GK | | | 22-0 | SPARE | D41856P | 27 | | | D40598P | 27 | | | 001-099 |
| 0332 | 22 | GA | | | 35-0 | SPARE | D40802J | 2 | | | D42176P | 26 | | | 001-099 |
| 0335 | 20 | PA | | | 44-0 | 28-22-11 | D03514 | 17 | | | D40594P | 55 | | | ALL |
| 0336 | 20 | PA | | | 1-0 | 28-22-11 | D03514 | 18 | | | SM00005 | | 9 | | ALL |
| 0337 | 18 | PA | | | 1-0 | 28-22-11 | D03514 | 27 | | | SM00005 | | 9 | | ALL |
| 0343 | 22 | GA | | | 10-0 | 33-16-42 | TB0114Z | 17 | BJ | | SM00012 | | 9 | | 001-099 |
| 0343 | 22 | GA | | | 11-0 | 33-16-42 | TB0114Z | 17 | BJ | | SM00012 | | 9 | | 115-199 |
| 0344 | 22 | GA | | | 10-0 | 33-16-42 | TB0114Z | 19 | BJ | | SM00009 | | 9 | | 001-099 |
| 0344 | 22 | GA | | | 11-0 | 33-16-42 | TB0114Z | 19 | BJ | | SM00009 | | 9 | | 115-199 |
| 0351 | 20 | GA | | | 4-0 | 33-51-11 | D04800 | 13 | | | GD00602 | DC.. | 2 | | 001-099 |
| 0351 | 20 | GA | | | 3-0 | 33-51-11 | D04800 | 13 | | | GD00602 | DC.. | 2 | | 115-199 |
| 0356 | 22 | GA | | | 5-0 | 29-11-12 | SM00014 | | 9 | | TB0113B | C021 | 2 | | 001-099 |
| 0356 | 22 | GA | | | 4-0 | 29-11-12 | SM00014 | | 9 | | TB0113B | C021 | 2 | | 115-199 |
| 0357 | 22 | GA | | | 2-0 | 29-11-12 | TB0113A | A022 | 2 | | TB0113B | A021 | 2 | | 001-099 |
| 0357 | 22 | GA | | | 1-0 | 29-11-12 | TB0113B | A021 | 2 | | TB0113A | A022 | 2 | | 115-199 |
| 0358 | 22 | GA | | | 5-0 | 29-11-12 | D03546 | 9 | | | TB0113A | C022 | 2 | | 001-099 |
| 0358 | 22 | GA | | | 5-0 | 29-11-12 | TB0113A | C022 | 2 | | D03546 | 9 | | | 115-199 |
| 0360 | 22 | GA | | | 4-0 | 33-51-11 | D04800 | 9 | | | GD00602 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0360 | 22 | | GA | | 3-0 | 33-51-11 | D04800 | | 9 | | GD00602 | DC.. | 2 | | 115-199 |
| 0361 | 22 | | GA | | 5-0 | 33-51-11 | D04800 | | 14 | | TB0113Z | 13 | BJ | | 001-099 |
| 0361 | 22 | | GA | | 4-0 | 33-51-11 | D04800 | | 14 | | TB0113Z | 13 | BJ | | 115-199 |
| 0362 | 22 | | GA | | 5-0 | 33-51-11 | D04800 | | 5 | | TB0113Z | 14 | BJ | | 001-099 |
| 0362 | 22 | | GA | | 4-0 | 33-51-11 | D04800 | | 5 | | TB0113Z | 14 | BJ | | 115-199 |
| 0363 | 22 | | GA | | 4-0 | 33-51-11 | D04800 | | 10 | | GD00602 | DC.. | 2 | | 001-099 |
| 0363 | 22 | | GA | | 3-0 | 33-51-11 | D04800 | | 10 | | GD00602 | DC.. | 2 | | 115-199 |
| 0364 | 22 | | GA | | 43-0 | 33-51-11 | D04800 | | 12 | | D41058P | 16 | | | 001-099 |
| 0364 | 22 | | GA | | 42-0 | 33-51-11 | D04800 | | 12 | | D41058P | 16 | | | 115-199 |
| 0365 | 20 | | GA | | 7-0 | 21-45-11 | D02722 | | 2 | | SM00001 | | 9 | | 001-099 |
| 0365 | 20 | | GA | | 6-0 | 21-45-11 | D02722 | | 2 | | SM00001 | | 9 | | 115-199 |
| 0366 | 20 | | GA | | 3-0 | 21-45-11 | D02722 | | 3 | | GD01728 | ST.. | E | | ALL |
| 0367 | 20 | | GA | | 10-0 | 21-45-11 | D01586 | | 1 | | D03094 | 4 | | | ALL |
| 0368 | 20 | | GA | | 6-0 | 21-45-11 | D01586 | | 2 | | SM00001 | | 9 | | ALL |
| 0369 | 20 | | GA | | 2-0 | 21-45-11 | D01586 | | 3 | | GD02831 | ST.. | E | | ALL |
| 0370 | 20 | | GA | | 3-0 | 21-45-11 | D01584 | | 1 | | SM00002 | | 9 | | ALL |
| 0371 | 20 | | GA | | 5-0 | 21-45-11 | D01584 | | 2 | | SM00001 | | 9 | | ALL |
| 0372 | 20 | | GA | | 4-0 | 21-45-11 | D02722 | | 1 | | SM00002 | | 9 | | ALL |
| 0373 | 20 | | GA | | 4-0 | 21-45-11 | D03094 | | 10 | | SM00002 | | 9 | | ALL |
| 0374 | 20 | | GA | | 6-0 | 21-45-11 | D01584 | | 3 | | GD01252 | ST.. | 2 | | 001-099 |
| 0374 | 20 | | GA | | 7-0 | 21-45-11 | D01584 | | 3 | | GD01252 | ST.. | 2 | | 115-199 |
| 0375 | 22 | | GA | | 45-0 | 24-51-24 | D40590P | | 2 | | TB0113X | C015 | BJ | | ALL |
| 0376 | 22 | | GA | | 45-0 | 24-51-14 | D40590P | | 3 | | TB0113X | D015 | BJ | | ALL |
| 0377 | 24 | | GK | | 27-0 | 21-44-11 | TB0114X | D014 | BJ | | TB0058X | B012 | BJ | | 001-099 |
| 0377 | 24 | | GK | | 29-0 | 21-44-11 | TB0114X | D014 | BJ | | TB0058X | B012 | BJ | | 115-199 |
| 0378 | 24 | | GK | | 35-0 | 21-44-11 | D41856P | | 43 | | TB0058X | C012 | BJ | | 001-099 |
| 0378 | 24 | | GK | | 36-0 | 21-44-11 | D41856P | | 43 | | TB0058X | C012 | BJ | | 115-199 |
| 0379 | 22 | | GA | | 42-0 | 32-61-21 | D41172J | | 5 | | D41876P | 2 | | | 001-099 |
| 0379 | 22 | | GA | | 41-0 | 32-61-21 | D41172J | | 5 | | D41876P | 2 | | | 115-199 |
| 0380 | 24 | | GK | | 14-0 | 33-11-31 | D41004P | | 21 | | TB0111X | D002 | BJ | | 001-099 |
| 0380 | 24 | | GK | | 16-0 | 33-11-31 | D41004P | | 21 | | M10549 | PWR | C | | 115-199 |
| 0382 | 22 | | GA | | 8-0 | 33-11-31 | M10549 | GND | C | | GD00602 | AC.. | 2 | | 115-199 |
| 0384 | 24 | | GK | | 8-0 | 33-13-32 | TB0111Y | C006 | BJ | | SM00007 | | 9 | | ALL |
| 0385 | 22 | | GA | | 18-0 | SPARE | D41860P | | 4 | | D40608P | 39 | | | 001-099 |
| 0385 | 22 | | GA | | 17-0 | SPARE | D41860P | | 4 | | D40608P | 39 | | | 115-199 |
| 0386 | 22 | | GA | | 36-0 | 32-42-11 | D40802J | | 33 | | D40608P | 37 | | | ALL |
| 0387 | 22 | | GA | | 18-0 | 32-42-11 | D41860P | | 6 | | D40608P | 38 | | | 001-099 |
| 0387 | 22 | | GA | | 17-0 | SPARE | D41860P | | 6 | | D40608P | 38 | | | 115-199 |
| 0388 | 22 | | GA | | 18-0 | 32-42-11 | D41860P | | 7 | | D40608P | 7 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 12

Oct 09/2008



WIRE LIST
D280N032

Section W2070
Page 13
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0425 | 20 | | GA | | 41-0 | SPARE | D40608P | 25 | | | D03502 | CAP | Y | | 115-199 |
| 0426 | 20 | | GA | | 39-0 | SPARE | D40608P | | CAP | Y | D03540 | CAP | Y | | 115-199 |
| 0427 | 24 | | GK | | 38-0 | 21-25-11 | D41856P | 53 | | | D03558 | 23 | | | 001-099 |
| 0427 | 24 | | GK | | 37-0 | 21-25-11 | D41856P | 53 | | | D03558 | 23 | | | 115-199 |
| 0428 | 24 | | GK | | 40-0 | 21-25-11 | D40608P | 28 | | | TB0113Y | A003 | BJ | | ALL |
| 0429 | 20 | | GA | | 41-0 | SPARE | D40608P | 29 | | | D03546 | CAP | Y | | 115-199 |
| 0430 | 22 | | GA | | 13-0 | 30-34-22 | D40608P | 31 | | | D41058P | 30 | | | 001-099 |
| 0430 | 22 | | GA | | 12-0 | 30-34-22 | D40608P | 31 | | | D41058P | 30 | | | 115-199 |
| 0431 | 22 | | GA | | 18-0 | 30-34-22 | D40608P | 32 | | | D42176P | 27 | | | 001-099 |
| 0431 | 22 | | GA | | 17-0 | 30-34-22 | D40608P | 32 | | | D42176P | 27 | | | 115-199 |
| 0432 | 22 | | GA | | 18-0 | 30-34-22 | D40608P | 33 | | | D42176P | 8 | | | 001-099 |
| 0432 | 22 | | GA | | 17-0 | 30-34-22 | D40608P | 33 | | | D42176P | 8 | | | 115-199 |
| 0433 | 20 | | GA | | 21-0 | SPARE | D40608P | 34 | | | D40970P | 29 | | | 001-099 |
| 0433 | 20 | | GA | | 22-0 | SPARE | D40608P | 34 | | | D40970P | 29 | | | 115-199 |
| 0434 | 22 | | GA | | 12-0 | 33-11-31 | D03532 | 13 | | | SM00006 | | 9 | | 115-199 |
| 0435 | 22 | | GA | | 12-0 | 33-11-31 | D03532 | 15 | | | SM00013 | | 9 | | 115-199 |
| 0437 | 20 | | GA | | 7-0 | 33-13-31 | TB0114Z | 7 | BJ | | D05824 | 1 | | | 115-199 |
| 0438 | 20 | | GA | | 7-0 | 33-13-31 | TB0114Z | 9 | BJ | | D05824 | 2 | | | 115-199 |
| 0439 | 20 | | GA | | 32-0 | SPARE | D41412P | 7 | | | D03514 | CAP | Y | | 001-099 |
| 0439 | 20 | | GA | | 29-0 | SPARE | D41412P | 7 | | | D03514 | 14 | | | 115-199 |
| 0441 | 20 | | GA | | 30-0 | SPARE | D41412P | 9 | | | D03546 | CAP | Y | | 115-199 |
| 0442 | 20 | | GA | | 33-0 | SPARE | D41412P | 10 | | | D03546 | CAP | Y | | 001-099 |
| 0442 | 20 | | GA | | 30-0 | SPARE | D41412P | 10 | | | D03546 | CAP | Y | | 115-199 |
| 0443 | 20 | | GA | | 30-0 | SPARE | D41412P | 11 | | | D03502 | CAP | Y | | 115-199 |
| 0444 | 20 | | GA | | 30-0 | SPARE | D41412P | 16 | | | D03502 | CAP | Y | | 115-199 |
| 0445 | 20 | | GA | | 30-0 | SPARE | D41412P | 17 | | | D03502 | CAP | Y | | 115-199 |
| 0446 | 20 | | GA | | 30-0 | SPARE | D41412P | 19 | | | D03532 | CAP | Y | | 115-199 |
| 0447 | 20 | | GA | | 30-0 | SPARE | D41412P | 21 | | | D03532 | CAP | Y | | 115-199 |
| 0448 | 20 | | GA | | 30-0 | SPARE | D41412P | 22 | | | D03532 | CAP | Y | | 115-199 |
| 0449 | 20 | | GA | | 33-0 | SPARE | D41412P | 23 | | | D03520 | CAP | Y | | 001-099 |
| 0449 | 20 | | GA | | 30-0 | SPARE | D41412P | 23 | | | D03520 | CAP | Y | | 115-199 |
| 0450 | 20 | | GA | | 33-0 | SPARE | D41412P | 24 | | | D03520 | CAP | Y | | 001-099 |
| 0450 | 20 | | GA | | 30-0 | SPARE | D41412P | 24 | | | D03520 | CAP | Y | | 115-199 |
| 0451 | 20 | | GA | | 27-0 | SPARE | D41412P | 25 | | | D03704 | CAP | Y | | 001-099 |
| 0451 | 20 | | GA | | 30-0 | SPARE | D41412P | 25 | | | D03520 | CAP | Y | | 115-199 |
| 0452 | 22 | | GA | | 26-0 | 27-51-21 | D41412P | 26 | | | D41172J | 35 | | | 001-099 |
| 0452 | 22 | | GA | | 22-0 | 27-51-21 | D41412P | 26 | | | D41172J | 35 | | | 115-199 |
| 0453 | 20 | | GA | | 29-0 | SPARE | D41412P | 27 | | | D03540 | CAP | Y | | 115-199 |
| 0454 | 20 | | GA | | 32-0 | SPARE | D41412P | 28 | | | D03540 | CAP | Y | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|-------|---------|-------------|------|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0454 | 20 | | GA | | 29-0 | SPARE | D41412P | 28 | | | | D03540 | CAP | Y | 115-199 |
| 0455 | 22 | | GA | | 26-0 | 27-51-21 | D41412P | 29 | | | | D41172J | 34 | | 001-099 |
| 0455 | 22 | | GA | | 22-0 | 27-51-21 | D41412P | 29 | | | | D41172J | 34 | | 115-199 |
| 0456 | 20 | | GA | | 27-0 | SPARE | D41412P | 30 | | | | D03704 | CAP | Y | 001-099 |
| 0456 | 20 | | GA | | 24-0 | SPARE | D41412P | 30 | | | | D03704 | CAP | Y | 115-199 |
| 0457 | 20 | | GA | | 24-0 | SPARE | D41412P | CAP | Y | | | D03704 | CAP | Y | 115-199 |
| 0458 | 20 | | GA | | 37-0 | SPARE | D41172J | 22 | | | | D41058P | 36 | | 001-099 |
| 0458 | 20 | | GA | | 35-0 | SPARE | D41172J | 22 | | | | D41058P | 36 | | 115-199 |
| 0461 | 20 | | GA | | 44-0 | SPARE | D03546 | CAP | Y | | | D41058P | CAP | Y | 115-199 |
| 0462 | 20 | | GA | | 44-0 | SPARE | D03546 | CAP | Y | | | D41058P | 40 | | 115-199 |
| 0463 | 20 | | GA | | 45-0 | SPARE | D03502 | CAP | Y | | | D41058P | CAP | Y | 001-099 |
| 0463 | 20 | | GA | | 44-0 | SPARE | D03502 | CAP | Y | | | D41058P | CAP | Y | 115-199 |
| 0464 | 20 | | GA | | 45-0 | SPARE | D03502 | CAP | Y | | | D41058P | 22 | | 001-099 |
| 0464 | 20 | | GA | | 44-0 | SPARE | D03502 | CAP | Y | | | D41058P | 42 | | 115-199 |
| 0465 | 20 | | GA | | 43-0 | SPARE | D03520 | CAP | Y | | | D41058P | 43 | | 115-199 |
| 0466 | 20 | | GA | | 43-0 | SPARE | D03520 | CAP | Y | | | D41058P | 44 | | 115-199 |
| 0467 | 20 | | GA | | 43-0 | SPARE | D03532 | CAP | Y | | | D41058P | 45 | | 115-199 |
| 0468 | 20 | | GA | | 43-0 | SPARE | D03532 | CAP | Y | | | D41058P | 50 | | 115-199 |
| 0469 | 20 | | GA | | 42-0 | SPARE | D03540 | CAP | Y | | | D41058P | 51 | | 115-199 |
| 0470 | 20 | | GA | | 42-0 | SPARE | D03540 | CAP | Y | | | D41058P | 52 | | 115-199 |
| 0471 | 20 | | GA | | 37-0 | SPARE | D03704 | CAP | Y | | | D41058P | 53 | | 115-199 |
| 0472 | 20 | | GA | | 38-0 | SPARE | D03704 | CAP | Y | | | D41058P | 19 | | 001-099 |
| 0472 | 20 | | GA | | 37-0 | SPARE | D03704 | CAP | Y | | | D41058P | 54 | | 115-199 |
| 0473 | 20 | | GA | | 37-0 | SPARE | D03704 | CAP | Y | | | D41058P | 55 | | 115-199 |
| 0474 | 22 | | GA | | 24-0 | SPARE | D41412P | 32 | | | | D41856P | 38 | | 001-099 |
| 0475 | 22 | | GA | | 24-0 | SPARE | D41412P | 33 | | | | D41856P | 44 | | 001-099 |
| 0476 | 22 | | GA | | 24-0 | SPARE | D41412P | 34 | | | | D41856P | 47 | | 001-099 |
| 0477 | 22 | | GA | | 24-0 | SPARE | D41412P | 35 | | | | D41856P | 52 | | 001-099 |
| 0478 | 24 | | GK | | 24-0 | 24-51-71 | D40608P | 36 | | | | D41470P | 9 | | ALL |
| 0479 | 24 | | GK | | 23-0 | 24-51-71 | D40590P | 6 | | | | D41860P | 5 | | 001-099 |
| 0479 | 22 | | GA | | 22-0 | 24-51-71 | D40590P | 6 | | | | D41860P | 5 | | 115-199 |
| 0480 | 24 | | GK | | 38-0 | 24-51-71 | D40592P | 5 | | | | TB0116X | A018 | BJ | 001-099 |
| 0480 | 24 | | GK | | 40-0 | 24-51-71 | D40592P | 5 | | | | TB0116X | A018 | BJ | 115-199 |
| 0481 | 18 | | GA | | 39-0 | 28-22-11 | SM00005 | | 9 | | | D41856P | 28 | 18 | 001-099 |
| 0481 | 18 | | GA | | 38-0 | 28-22-11 | SM00005 | | 9 | | | D41856P | 28 | 18 | 115-199 |
| 0484 | 24 | | GK | | 17-0 | SPARE | D40598P | 6 | | | | D41058P | 39 | | 001-099 |
| 0485 | 20 | | GA | | 6-0 | 33-13-71 | D02896 | 7 | | | | GD00617 | ST.. | 2 | 115-199 |
| 0486 | 24 | | GK | | 46-0 | 24-41-11 | D40590P | 7 | | | | TB0115X | A002 | BJ | ALL |
| 0487 | 24 | | GK | | 37-0 | 33-22-11 | D41106J | 3 | | | | D41412P | 31 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0487 | 22 | | GA | | 28-0 | 33-22-11 | | D41412P | | 31 | | D41106J | | 3 | | 115-199 |
| 0488 | 20 | | GA | | 9-0 | 33-22-11 | | D41106J | | 4 | | GD00602 | AC.. | 2 | | 001-099 |
| 0488 | 20 | | GA | | 12-0 | 33-22-11 | | GD00602 | AC.. | 2 | | D41106J | | 4 | | 115-199 |
| 0500 | 20 | | GA | | 9-0 | 33-13-32 | | D03414 | | 8 | | TB0115X | A019 | BJ | | ALL |
| 0501 | 20 | | GA | | 9-0 | 33-13-32 | | D03408 | | 8 | | TB0115X | A020 | BJ | | ALL |
| 0502 | 22 | | GA | | 5-0 | 33-51-11 | | D04800 | | 16 | | TB0113X | A015 | BJ | | 001-099 |
| 0502 | 22 | | GA | | 4-0 | 33-51-11 | | D04800 | | 16 | | TB0113X | A015 | BJ | | 115-199 |
| 0503 | 20 | | GA | | 45-0 | 28-22-11 | | D42166P | | 2 | | D03514 | | 24 | | ALL |
| 0504 | 20 | | GA | | 23-0 | 28-22-11 | | D42176P | | 4 | | D42166P | | 1 | | 001-099 |
| 0504 | 20 | | GA | | 22-0 | 28-22-11 | | D42166P | | 1 | | D42176P | | 4 | | 115-199 |
| 0505 | 20 | | GA | | 39-0 | 28-22-11 | | D41856P | | 51 | | D03514 | | 28 | | 001-099 |
| 0505 | 20 | | GA | | 38-0 | 28-22-11 | | D41856P | | 51 | | D03514 | | 28 | | 115-199 |
| 0506 | 20 | | GA | | 39-0 | 28-22-11 | | D42176P | | 1 | | D03514 | | 13 | | ALL |
| 0507 | 20 | | GA | | 39-0 | 28-22-11 | | D42176P | | 3 | | D03514 | | 26 | | 001-099 |
| 0507 | 20 | | GA | | 39-0 | 28-22-11 | | D03514 | | 26 | | D42176P | | 3 | | 115-199 |
| 0508 | 20 | | GA | | 39-0 | 28-22-11 | | D42176P | | 2 | | D03514 | | 12 | | ALL |
| 0509 | 22 | | GA | | 23-0 | SPARE | | D42166P | | 3 | | D42176P | | 5 | | 001-099 |
| 0509 | 22 | | GA | | 22-0 | SPARE | | D42166P | | 3 | | D42176P | | 5 | | 115-199 |
| 0510 | 22 | | GA | | 23-0 | SPARE | | D42166P | | 4 | | D42176P | | 6 | | 001-099 |
| 0510 | 22 | | GA | | 22-0 | SPARE | | D42166P | | 4 | | D42176P | | 6 | | 115-199 |
| 0511 | 22 | | GA | | 12-0 | 24-25-11 | | D40802J | | 11 | | D03704 | | 27 | | 001-099 |
| 0511 | 22 | | GA | | 12-0 | 24-25-11 | | D03704 | | 27 | | D40802J | | 11 | | 115-199 |
| 0512 | 22 | | GA | | 7-0 | 24-25-11 | | D03704 | | 26 | | TB0121X | A017 | BJ | | ALL |
| 0513 | 22 | | GA | | 30-0 | SPARE | | D42166P | | 7 | | D41470P | | 34 | | 001-099 |
| 0513 | 22 | | GA | | 29-0 | SPARE | | D42166P | | 7 | | D41470P | | 34 | | 115-199 |
| 0514 | 22 | | GA | | 30-0 | SPARE | | D42166P | | 8 | | D41470P | | 35 | | 001-099 |
| 0514 | 22 | | GA | | 29-0 | SPARE | | D42166P | | 8 | | D41470P | | 35 | | 115-199 |
| 0515 | 20 | | GA | | 12-0 | 30-71-11 | | D41470P | | 24 | | D41860P | | 24 | | 001-099 |
| 0515 | 20 | | GA | | 15-0 | 30-71-11 | | D41470P | | 24 | | D41860P | | 24 | | 115-199 |
| 0518 | 22 | | GA | | 15-0 | SPARE | | D42176P | | 9 | | D41470P | | 36 | | 115-199 |
| 0519 | 22 | | GA | | 15-0 | SPARE | | D42176P | | 10 | | D41470P | | 37 | | 115-199 |
| 0522 | 22 | | GA | | 11-0 | SPARE | | D42176P | | 13 | | D40592P | | 20 | | 115-199 |
| 0523 | 22 | | GA | | 11-0 | SPARE | | D42176P | | 14 | | D40592P | | 21 | | 115-199 |
| 0524 | 22 | | GA | | 21-0 | SPARE | | D42176P | | 15 | | D40970P | | 30 | | 115-199 |
| 0525 | 22 | | GA | | 21-0 | SPARE | | D42176P | | 17 | | D40970P | | 31 | | 115-199 |
| 0526 | 20 | | GA | | 23-0 | SPARE | | D42176P | | 16 | | D42166P | | 5 | | 001-099 |
| 0526 | 20 | | GA | | 23-0 | 28-25-11 | | D42176P | | 16 | | D42166P | | 5 | | 115-199 |
| 0527 | 24 | | GK | | 33-0 | 34-12-22 | | D42176P | | 18 | | D03704 | | 5 | | 001-099 |
| 0527 | 24 | | GK | | 34-0 | 34-12-22 | | D42176P | | 18 | | D03704 | | 5 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0528 | 22 | GA | | | 6-0 | 34-12-22 | D03704 | | 4 | | GD00617 | DC.. | 2 | | ALL |
| 0533 | 22 | GA | | | 39-0 | SPARE | D41856P | | 34 | | D03520 | CAP | Y | | 001-099 |
| 0534 | 22 | GA | | | 9-0 | 23-51-21 | D40802J | | 8 | | TB0113A | A010 | 2 | | 001-099 |
| 0535 | 22 | GA | | | 9-0 | 23-51-21 | D40802J | | 9 | | TB0113A | A009 | 2 | | 001-099 |
| 0536 | 22 | GA | | | 2-0 | 23-51-21 | TB0113A | C009 | 2 | | TB0113A | C010 | 2 | | 001-099 |
| 0537 | 22 | GA | | | 9-0 | 32-42-12 | D40802J | | 6 | | TB0113A | A024 | 2 | | 001-099 |
| 0561 | 22 | GA | | | 5-0 | 33-51-11 | D04800 | | 3 | | TB0113X | B015 | BJ | | 001-099 |
| 0561 | 22 | GA | | | 4-0 | 33-51-11 | D04800 | | 3 | | TB0113X | B015 | BJ | | 115-199 |
| 0578 | 24 | GK | | | 33-0 | 31-31-62 | D41876P | | 4 | | D41470P | | 39 | | 001-099 |
| 0591 | 20 | GA | | | 4-0 | 28-43-11 | D06870 | | 10 | | GD00602 | ST.. | 2 | | 001-099 |
| 0591 | 18 | GA | | | 4-0 | 28-43-11 | D06870 | | 10 | 18 | GD00602 | ST.. | 2 | | 115-199 |
| 0603 | 20 | GA | | | 4-0 | 28-41-11 | D06870 | | 11 | | GD00602 | DC.. | 2 | | ALL |
| 0604 | 24 | GK | | | 23-0 | 24-27-21 | D42176P | | 11 | | D42166P | | 6 | | 001-099 |
| 0604 | 24 | GK | | | 22-0 | 24-27-21 | D42176P | | 11 | | D42166P | | 6 | | 115-199 |
| 0605 | 18 | GA | | | 15-0 | 28-22-11 | D41856P | | 45 | 18 | SP01912 | | 9 | | 003-099 |
| 0606 | 18 | GA | | | 15-0 | 28-22-11 | D41856P | | 46 | 18 | SP01914 | | 9 | | 003-099 |
| 0614 | 20 | GA | | | 8-0 | 33-13-32 | TB0115Y | A018 | BJ | | D07666 | | 12 | | 001-099 |
| 0614 | 20 | GA | | | 13-0 | 33-13-32 | TB0115Y | A018 | BJ | | D07666 | | 12 | | 115-199 |
| 0615 | 20 | GA | | | 8-0 | 33-13-32 | TB0115Y | C017 | BJ | | D07668 | X1 | | | 001-099 |
| 0615 | 20 | GA | | | 13-0 | 33-13-32 | SP01934 | | 9 | | D07668 | X1 | | | 115-199 |
| 0616 | 20 | GA | | | 9-0 | 33-13-32 | TB0113Y | C006 | BJ | | D07668 | X2 | | | 001-099 |
| 0616 | 20 | GA | | | 13-0 | 33-13-32 | SP01936 | | 9 | | D07668 | X2 | | | 115-199 |
| 0617 | 20 | GA | | | 1-0 | 33-13-32 | D07666 | | 6 | | D07666 | | 5 | | ALL |
| 0618 | 20 | GA | | | 9-0 | 33-13-32 | D07666 | | 11 | | GD00601 | AC.. | 2 | | 001-099 |
| 0618 | 20 | GA | | | 14-0 | 33-13-32 | D07666 | | 11 | | GD00601 | AC.. | 2 | | 115-199 |
| 0619 | 20 | GA | | | 9-0 | 33-13-32 | D07666 | | 7 | | GD00601 | ST.. | 2 | | 001-099 |
| 0619 | 20 | GA | | | 14-0 | 33-13-32 | D07666 | | 7 | | GD00601 | ST.. | 2 | | 115-199 |
| 0620 | 20 | GA | | | 2-0 | 33-13-32 | D07666 | | 2 | | D07668 | A3 | | | 001-099 |
| 0620 | 20 | GA | | | 3-0 | 33-13-32 | D07666 | | 2 | | D07668 | A3 | | | 115-199 |
| 0621 | 20 | GA | | | 8-0 | 33-13-32 | D07668 | A2 | | | TB0115X | D020 | BJ | | 001-099 |
| 0621 | 20 | GA | | | 13-0 | 33-13-32 | D07668 | A2 | | | TB0115X | D020 | BJ | | 115-199 |
| 0622 | 20 | GA | | | 8-0 | 33-13-32 | D07668 | A1 | | | TB0115X | B020 | BJ | | 001-099 |
| 0622 | 20 | GA | | | 13-0 | 33-13-32 | D07668 | A1 | | | TB0115X | B020 | BJ | | 115-199 |
| 0623 | 20 | GA | | | 8-0 | 28-22-32 | D40802J | | 35 | | D03514 | | 19 | | 009-099 |
| 0624 | 20 | GA | | | 39-0 | 28-22-32 | D03514 | | 1 | | D41860P | | 15 | | 009-099 |
| 0625 | 20 | GA | | | 39-0 | 28-22-32 | D03514 | | 2 | | D41860P | | 17 | | 009-099 |
| 0626 | 20 | GA | | | 31-0 | 28-22-32 | D03514 | | 22 | | D41412P | | 36 | | 009-099 |
| 0627 | 20 | GA | | | 31-0 | 28-22-32 | D03514 | | 9 | | D41412P | | 40 | | 009-099 |
| 0628 | 20 | GA | | | 31-0 | 28-22-32 | D03514 | | 10 | | D41412P | | 39 | | 009-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2070 | 286N2070 | | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | | |
| 0629 | 20 | | GA | | 23-0 | 28-22-32 | D41412P | 38 | | | D41860P | 18 | | | 009-099 | | |
| 0630 | 20 | | GA | | 28-0 | 28-22-32 | D41412P | 37 | | | D41058P | 46 | | | 009-099 | | |
| 0631 | 20 | | GA | | 28-0 | 28-22-32 | D41412P | 41 | | | D41058P | 47 | | | 009-099 | | |
| 0635 | 24 | | GK | | 18-0 | 24-11-21 | D40598P | 14 | | | D41058P | 41 | | | 001-099 | | |
| 0635 | 24 | | GK | | 17-2 | 24-11-21 | D40598P | 14 | | | D41058P | 41 | | | 115-199 | | |
| 0800 | 20 | | GA | | 43-0 | SPARE | D03532 | 22 | | | D41058P | CAP | Y | | 115-199 | | |
| 0801 | 20 | | GA | | 7-0 | 33-45-11 | D03532 | 24 | | | GD00606 | AC.. | 2 | | ALL | | |
| 0802 | 22 | | GA | | 29-0 | 33-45-11 | D03532 | 23 | | | TB0059X | A004 | BJ | | ALL | | |
| 0803 | 18 | | GA | | 43-0 | SPARE | D03532 | 21 | 18 | | D41058P | 38 | 18 | | 115-199 | | |
| 0804 | 24 | | GK | | 21-0 | 34-22-93 | D40802J | 13 | | | D41172J | 33 | | | 115-199 | | |
| 0805 | 24 | | GK | | 21-0 | 34-22-93 | D40802J | 14 | | | D41172J | 32 | | | 115-199 | | |
| 0806 | 24 | | GK | | 17-0 | 34-22-93 | D41172J | 30 | | | TB0059X | C008 | BJ | | 115-199 | | |
| 0807 | 22 | | GA | | 8-0 | 24-51-72 | D03502 | 42 | | | TB0116X | C017 | BJ | | ALL | | |
| 0808 | 22 | | GA | | 8-0 | 24-51-72 | D03502 | 43 | | | TB0116X | D017 | BJ | | ALL | | |
| 0809 | 22 | | GA | | 21-0 | 34-55-21 | D40802J | 31 | | | D41172J | 31 | | | 115-199 | | |
| 0810 | 22 | | GA | | 9-0 | 23-51-21 | D40802J | 32 | | | TB0113Y | C017 | BJ | | 115-199 | | |
| 0811 | 22 | | GA | | 33-0 | 33-22-11 | D41470P | 38 | | | D41876P | 30 | | | ALL | | |
| 2001B | 24 | | GL | AB | 49-0 | SPARE | D03536 | 20 | | | D41876P | CAP | Y | | 115-199 | | |
| 2001R | 24 | | GL | AB | 0-0 | SPARE | D03536 | 39 | | | D41876P | 6 | | | 115-199 | | |
| 2002B | 24 | | GL | AC | 49-0 | SPARE | D03536 | 19 | | | D41876P | CAP | Y | | 115-199 | | |
| 2002R | 24 | | GL | AC | 0-0 | SPARE | D03536 | 18 | | | D41876P | CAP | Y | | 115-199 | | |
| 2003B | 24 | | GL | AD | 49-0 | SPARE | D03536 | 32 | | | D41876P | 11 | | | 115-199 | | |
| 2003R | 24 | | GL | AD | 0-0 | SPARE | D03536 | 16 | | | D41876P | 10 | | | 115-199 | | |
| 2006B | 24 | | GL | DG | 38-0 | 36-21-11 | D03540 | 8 | | | D41856P | 4 | | | ALL | | |
| 2006R | 24 | | GL | DG | 0-0 | 36-21-11 | D03540 | 7 | | | D41856P | 3 | | | ALL | | |
| 2008B | 24 | | GL | DD | 49-0 | SPARE | D03536 | 10 | | | D41876P | 13 | | | 115-199 | | |
| 2008R | 24 | | GL | DD | 0-0 | SPARE | D03536 | 24 | | | D41876P | 12 | | | 115-199 | | |
| 2009B | 24 | | GL | DE | 49-0 | 28-41-11 | D03536 | 12 | | | D41876P | CAP | Y | | 115-199 | | |
| 2009R | 24 | | GL | DE | 0-0 | 28-41-11 | D03536 | 11 | | | D41876P | CAP | Y | | 115-199 | | |
| 2010B | 24 | | GL | DF | 49-0 | 28-41-11 | D03536 | 29 | | | D41876P | CAP | Y | | 115-199 | | |
| 2010R | 24 | | GL | DF | 0-0 | 28-41-11 | D03536 | 13 | | | D41876P | CAP | Y | | 115-199 | | |
| 2032B | 24 | | GL | BP | 22-0 | 21-31-21 | D40598P | 4 | | | D41856P | 48 | | | 001-099 | | |
| 2032B | 24 | | GL | BP | 21-0 | 21-31-21 | D40598P | 4 | | | D41856P | 48 | | | 115-199 | | |
| 2032R | 24 | | GL | BP | 0-0 | 21-31-21 | D40598P | 5 | | | D41856P | 49 | | | ALL | | |
| 2034B | 22 | | GB | AE | 6-0 | 29-11-22 | D03710 | 20 | | | TB0121X | C003 | BJ | | 115-199 | | |
| 2034R | 22 | | GB | AE | 0-0 | 29-11-22 | D03710 | 21 | | | TB0121X | D003 | BJ | | 115-199 | | |
| 2035B | 22 | | GB | AG | 34-0 | 29-11-12 | D40592P | 7 | | | TB0121X | A004 | BJ | | 115-199 | | |
| 2035R | 22 | | GB | AG | 0-0 | 29-11-12 | D40592P | 8 | | | TB0121X | B004 | BJ | | 115-199 | | |
| 2070B | 18 | | GB | AK | 49-0 | 28-43-11 | D06870 | 8 | 18 | | D41876P | 13 | 18 | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|---------|-------|------|-------------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 2070B | 18 | GB | AK | | 49-0 | 28-43-11 | D06870 | 8 | 18 | | SP01930 | | 9 | | 115-199 |
| 2070R | 18 | GB | AK | | 0-0 | 28-43-11 | D06870 | 9 | 18 | | D41876P | 12 | 18 | | 001-099 |
| 2070R | 18 | GB | AK | | 0-0 | 28-43-11 | D06870 | 9 | 18 | | SP01932 | | 9 | | 115-199 |
| 2501B | 22 | GU | BM | | 30-0 | 28-21-21 | D41876P | 20 | | | D40970P | 8 | | | 001-099 |
| 2501B | 22 | GU | BM | | 31-0 | 28-21-21 | D41876P | 20 | | | D40970P | 8 | | | 115-199 |
| 2501R | 22 | GU | BM | | 0-0 | 28-21-21 | D41876P | 19 | | | D40970P | 7 | | | ALL |
| 2501Z | | | BM | | 0-0 | 28-21-21 | D41876P | 21 | | | D40970P | 9 | | | ALL |
| 2502B | 22 | GU | BN | | 30-0 | 28-21-21 | D41876P | 23 | | | D40970P | 24 | | | 001-099 |
| 2502B | 22 | GU | BN | | 31-0 | 28-21-21 | D41876P | 23 | | | D40970P | 24 | | | 115-199 |
| 2502R | 22 | GU | BN | | 0-0 | 28-21-21 | D41876P | 22 | | | D40970P | 23 | | | ALL |
| 2502Z | | | BN | | 0-0 | 28-21-21 | D41876P | 24 | | | D40970P | 25 | | | ALL |
| 2503B | 24 | G2 | AW | | 17-0 | 33-11-11 | D41172J | 3 | | | D41004P | 14 | | | 001-099 |
| 2503B | 24 | G2 | AW | | 18-0 | 33-11-11 | D41172J | 3 | | | D41004P | 14 | | | 115-199 |
| 2503R | 24 | G2 | AW | | 0-0 | 33-11-11 | D41172J | 4 | | | D41004P | 15 | | | ALL |
| 2503Z | | | AW | | 0-0 | 33-11-11 | D41172J | 39 | | | GD01221 | ST.. | 2 | | ALL |
| 2509B | 22 | GU | DE | | 49-0 | 28-41-11 | D06870 | 4 | | | D41876P | 15 | | | 001-099 |
| 2509B | 22 | GU | ED | | 49-0 | 28-41-11 | D06870 | 4 | | | D41876P | 15 | | | 115-199 |
| 2509R | 22 | GU | DE | | 0-0 | 28-41-11 | D06870 | 5 | | | D41876P | 14 | | | 001-099 |
| 2509R | 22 | GU | ED | | 0-0 | 28-41-11 | D06870 | 5 | | | D41876P | 14 | | | 115-199 |
| 2509Z | | | DE | | 0-0 | 28-41-11 | GD00602 | ST.. | 2 | | D41876P | 17 | | | 001-099 |
| 2509Z | | | ED | | 0-0 | 28-41-11 | GD00602 | ST.. | 2 | | D41876P | 17 | | | 115-199 |
| 3001B | 24 | GM | AA | | 9-0 | 33-13-61 | D03532 | 6 | | | D40802J | 38 | | | ALL |
| 3001R | 24 | GM | AA | | 0-0 | 33-13-61 | D03532 | 10 | | | D40802J | 37 | | | ALL |
| 3001Y | 24 | GM | AA | | 0-0 | 33-13-61 | D03532 | 11 | | | D40802J | 39 | | | ALL |
| 3002B | 24 | GM | DB | | 38-0 | 21-61-31 | D03558 | 19 | | | D41856P | 24 | | | 001-099 |
| 3002B | 24 | GM | DB | | 37-0 | 21-61-31 | D03558 | 19 | | | D41856P | 24 | | | 115-199 |
| 3002R | 24 | GM | DB | | 0-0 | 21-61-31 | D03558 | 18 | | | D41856P | 23 | | | ALL |
| 3002Y | 24 | GM | DB | | 0-0 | 21-61-31 | D03558 | 20 | | | D41856P | 25 | | | ALL |
| 3003B | 24 | GM | DC | | 38-0 | 21-61-21 | D03558 | 43 | | | D41856P | 18 | | | 001-099 |
| 3003B | 24 | GM | DC | | 37-0 | 21-61-21 | D03558 | 43 | | | D41856P | 18 | | | 115-199 |
| 3003R | 24 | GM | DC | | 0-0 | 21-61-21 | D03558 | 42 | | | D41856P | 17 | | | ALL |
| 3003Y | 24 | GM | DC | | 0-0 | 21-61-21 | D03558 | 44 | | | D41856P | 19 | | | ALL |
| 3004B | 24 | GM | EA | | 23-0 | 28-41-14 | D41876P | 9 | | | D40608P | 20 | | | 001-099 |
| 3004B | 24 | GM | EA | | 24-0 | 28-41-14 | D41876P | 9 | | | D40608P | 20 | | | 115-199 |
| 3004R | 24 | GM | EA | | 0-0 | 28-41-14 | D41876P | 7 | | | D40608P | 26 | | | ALL |
| 3004Y | 24 | GM | EA | | 0-0 | 28-41-14 | D41876P | 8 | | | D40608P | 22 | | | ALL |
| 3008B | 24 | GM | AR | | 3-0 | 33-13-32 | D03414 | 5 | | | SM00003 | | 9 | | 001-099 |
| 3008B | 24 | GM | AR | | 2-0 | 33-13-32 | D03414 | 5 | | | SM00003 | | 9 | | 115-199 |
| 3008R | 24 | GM | AR | | 0-0 | 33-13-32 | D03414 | 6 | | | SM00004 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2070 | 286N2070 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 3008Y | 24 | GM | AR | | 0-0 | 33-13-32 | D03414 | | 1 | | SM00005 | | 9 | | ALL |
| 3009B | 24 | GM | AS | | 1-0 | 33-13-32 | D03408 | | 5 | | SM00003 | | 9 | | ALL |
| 3009R | 24 | GM | AS | | 0-0 | 33-13-32 | D03408 | | 6 | | SM00004 | | 9 | | ALL |
| 3009Y | 24 | GM | AS | | 0-0 | 33-13-32 | D03408 | | 1 | | SM00005 | | 9 | | ALL |
| 3011B | 24 | GM | AF | | 18-0 | 33-13-71 | D41172J | | 24 | | D02896 | | 5 | | 115-199 |
| 3011R | 24 | GM | AF | | 0-0 | 33-13-71 | D41172J | | 25 | | D02896 | | 6 | | 115-199 |
| 3011Y | 24 | GM | AF | | 0-0 | 33-13-71 | D41172J | | 26 | | D02896 | | 1 | | 115-199 |
| 3012B | 24 | GM | DM | | 38-0 | 21-61-11 | D03558 | | 36 | | D41856P | | 11 | | 001-099 |
| 3012B | 24 | GM | DM | | 37-0 | 21-61-11 | D03558 | | 36 | | D41856P | | 11 | | 115-199 |
| 3012R | 24 | GM | DM | | 0-0 | 21-61-11 | D03558 | | 35 | | D41856P | | 10 | | ALL |
| 3012Y | 24 | GM | DM | | 0-0 | 21-61-11 | D03558 | | 37 | | D41856P | | 12 | | ALL |
| 3014B | 24 | GM | AT | | 9-0 | 33-13-31 | D03532 | | 16 | | TB0111Y | C005 | BJ | | ALL |
| 3014R | 24 | GM | AT | | 0-0 | 33-13-31 | D03532 | | 1 | | TB0111Y | A006 | BJ | | ALL |
| 3014Y | 24 | GM | AT | | 0-0 | 33-13-31 | D03532 | | 2 | | TB0111Y | A005 | BJ | | ALL |
| 3017B | 24 | GM | AV | | 8-0 | 33-13-32 | TB0111Y | C005 | BJ | | SM00003 | | 9 | | ALL |
| 3017R | 24 | GM | AV | | 0-0 | 33-13-32 | TB0111Y | A006 | BJ | | SM00004 | | 9 | | ALL |
| 3017Y | 24 | GM | AV | | 0-0 | 33-13-32 | TB0111Y | A005 | BJ | | SM00005 | | 9 | | ALL |
| 5003B | 22 | GU | DN | | 18-0 | 32-42-11 | D41860P | | 8 | | D40608P | | 8 | | 001-099 |
| 5003B | 22 | GU | BQ | | 17-0 | 32-42-11 | D41860P | | 8 | | D40608P | | 8 | | 115-199 |
| 5003R | 22 | GU | DN | | 0-0 | 32-42-11 | D41860P | | 9 | | D40608P | | 9 | | 001-099 |
| 5003R | 22 | GU | BQ | | 0-0 | 32-42-11 | D41860P | | 9 | | D40608P | | 9 | | 115-199 |
| 5003Z | | | DN | | 0-0 | 32-42-11 | D41860P | | 10 | | D40608P | | 10 | | 001-099 |
| 5003Z | | | BQ | | 0-0 | 32-42-11 | D41860P | | 10 | | D40608P | | 10 | | 115-199 |
| A-BK | | | | | 0-0 | 33-51-12 | R10238 | BLK | | | GD00602 | DC.. | 2 | | 115-199 |
| A-WT | | | | | 0-0 | 33-51-12 | D05262 | | 1 | VG | R10238 | WHT | | | 115-199 |
| W2071 | 286N2071 | | | VHF-L CONTROL, P8 TO E4-3 | | | | | | | | | | | |
| 0001 | 20 | GA | | | 6-0 | 33-13-52 | D00123 | | 1 | | TB0159Z | 11 | BJ | | 001-099 |
| 0001 | 20 | GA | | | 5-0 | 33-13-52 | D00123 | | 1 | | TB0159Z | 11 | BJ | | 115-199 |
| 0002 | 20 | GA | | | 7-0 | 33-13-52 | D00123 | | 2 | | GD01649 | AC.. | 2 | | 001-099 |
| 0002 | 20 | GA | | | 5-0 | 33-13-52 | D00123 | | 2 | | GD01649 | AC.. | 2 | | 115-199 |
| 0003 | 18 | GA | | | 42-0 | 23-12-11 | D00123 | | 13 | 18 | D41531P | | 7 | | ALL |
| 0005 | 24 | GK | | | 42-0 | 23-12-11 | D00123 | | 5 | | D41531P | | 5 | | ALL |
| 0006 | 24 | GK | | | 42-0 | 23-12-11 | D00123 | | 6 | | D41531P | | 6 | | ALL |
| 0007 | 24 | GK | | | 42-0 | 23-12-11 | D00123 | | 7 | | D41531P | | 1 | | ALL |
| 0008 | 24 | GK | | | 42-0 | 23-12-11 | D00123 | | 8 | | D41531P | | 8 | | ALL |
| 0009 | 24 | GK | | | 42-0 | 23-12-11 | D00123 | | 9 | | D41531P | | 9 | | ALL |
| 0010 | 20 | GA | | | 7-0 | 23-12-11 | D00123 | | 14 | | GD00082 | DC.. | 2 | | 001-099 |
| 0010 | 20 | GA | | | 5-0 | 23-12-11 | D00123 | | 14 | | GD00082 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2071 | 286N2071 | | | VHF-L CONTROL, P8 TO E4-3 (continued) | | | | | | | | | | | |
| 5001B | 24 | | G2 | AA | 42-0 | 23-12-11 | D00123 | 18 | | | D41531P | 12 | | | ALL |
| 5001R | 24 | | G2 | AA | 0-0 | 23-12-11 | D00123 | 17 | | | D41531P | 11 | | | ALL |
| 5001Z | | | | AA | 0-0 | 23-12-11 | D00123 | 19 | | | D41531P | 3 | | | ALL |
| W2072 | 286N2072 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM | | | | | | | | | | | |
| 0001 | 24 | | GK | | 10-0 | 30-32-11 | D40804J | 3 | | | TB0113Y | A006 | BJ | | ALL |
| 0002 | 24 | | GK | | 38-0 | 30-32-11 | D03566 | 18 | | | D40594P | 26 | | | ALL |
| 0003 | 20 | | GA | | 25-0 | 31-41-19 | D40804J | 5 | | | TB0101X | C002 | BJ | | 001-099 |
| 0003 | 20 | | GA | | 26-0 | 31-41-19 | D40804J | 5 | | | TB0101X | C002 | BJ | | 115-199 |
| 0004 | 22 | | GA | | 38-0 | 27-62-11 | D03566 | 5 | | | D40594P | 2 | | | 001-099 |
| 0004 | 20 | | GA | | 38-0 | 27-62-11 | D03566 | 5 | | | D40594P | 2 | | | 115-199 |
| 0005 | 24 | | GK | | 38-0 | 30-32-11 | D40594P | 42 | | | TB0113Y | A006 | BJ | | ALL |
| 0006 | 22 | | GA | | 36-0 | 30-41-12 | D03554 | 11 | | | D41872P | 2 | | | 001-099 |
| 0006 | 22 | | GA | | 35-0 | 30-41-12 | D03554 | 11 | | | D41872P | 2 | | | 115-199 |
| 0007 | 22 | | GA | | 36-0 | 30-41-12 | D03554 | 12 | | | D41872P | 3 | | | 001-099 |
| 0007 | 22 | | GA | | 35-0 | 30-41-12 | D03554 | 12 | | | D41872P | 3 | | | 115-199 |
| 0008 | 22 | | GA | | 36-0 | 30-41-12 | D03554 | 10 | | | D41872P | 4 | | | 001-099 |
| 0008 | 22 | | GA | | 35-0 | 30-41-12 | D03554 | 10 | | | D41872P | 4 | | | 115-199 |
| 0009 | 22 | | GA | | 36-0 | 30-41-12 | D03554 | 13 | | | D41872P | 1 | | | 001-099 |
| 0009 | 22 | | GA | | 35-0 | 30-41-12 | D03554 | 13 | | | D41872P | 1 | | | 115-199 |
| 0010 | 22 | | GA | | 7-0 | 33-16-42 | D03513 | 4 | | | TB0114Z | 18 | BJ | | ALL |
| 0014 | 20 | | GA | | 11-0 | 33-44-11 | D03507 | 5 | | | D40804J | 1 | | | ALL |
| 0015 | 20 | | GA | | 39-0 | 33-44-11 | D03507 | 6 | | | D40594P | 1 | | | ALL |
| 0016 | 24 | | GK | | 38-0 | SPARE | D03566 | 2 | | | D40594P | 44 | | | 115-199 |
| 0017 | 22 | | GA | | 6-0 | 33-16-42 | D03566 | 15 | | | TB0114Z | 16 | BJ | | ALL |
| 0020 | 22 | | GA | | 6-0 | 33-16-42 | D03566 | 16 | | | TB0114Z | 20 | BJ | | ALL |
| 0021 | 22 | | GA | | 1-0 | 33-16-42 | TB0114Z | 17 | BJ | | TB0114Z | 18 | BJ | | ALL |
| 0022 | 20 | | GA | | 10-0 | 33-42-21 | D40804J | 29 | | | TB0113X | C012 | BJ | | ALL |
| 0024 | 20 | | GA | | 39-0 | 33-41-11 | D03507 | 8 | | | D40594P | 4 | | | ALL |
| 0026 | 24 | | GK | | 42-0 | 33-24-11 | D03517 | 11 | | | D41848P | 3 | | | 001-099 |
| 0026 | 22 | | GA | | 42-0 | 33-24-11 | D03517 | 11 | | | D41848P | 3 | | | 115-199 |
| 0028 | 20 | | GA | | 43-0 | 33-42-21 | D41848P | 14 | | | TB0113X | D012 | BJ | | ALL |
| 0032 | 24 | | GK | | 42-0 | 33-24-11 | D03517 | 10 | | | D41848P | 4 | | | 001-099 |
| 0032 | 22 | | GA | | 42-0 | 33-24-11 | D03517 | 10 | | | D41848P | 4 | | | 115-199 |
| 0034 | 22 | | GA | | 38-0 | 32-42-11 | D03566 | 12 | | | D40594P | 10 | | | ALL |
| 0035 | 24 | | GK | | 42-0 | 33-24-11 | D03517 | 7 | | | D41848P | 6 | | | 001-099 |
| 0035 | 22 | | GA | | 42-0 | 33-24-11 | D03517 | 7 | | | D41848P | 6 | | | 115-199 |
| 0036 | 24 | | GK | | 42-0 | 33-24-11 | D03517 | 6 | | | D41848P | 5 | | | 001-099 |
| 0036 | 22 | | GA | | 42-0 | 33-24-11 | D03517 | 6 | | | D41848P | 5 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2072 | 286N2072 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | | |
| 0037 | 24 | | GK | | 5-0 | 33-24-11 | D03517 | | 8 | | | GD00610 | DC.. | 2 | | 001-099 |
| 0037 | 20 | | GA | | 5-0 | 33-24-11 | D03517 | | 8 | | | GD00610 | DC.. | 2 | | 115-199 |
| 0038 | 24 | | GK | | 5-0 | 33-24-11 | D03517 | | 5 | | | GD00610 | DC.. | 2 | | 001-099 |
| 0038 | 20 | | GA | | 5-0 | 33-24-11 | D03517 | | 5 | | | GD00610 | DC.. | 2 | | 115-199 |
| 0039 | 24 | | GK | | 38-0 | 30-31-12 | D03566 | | 7 | | | D40594P | | 11 | | ALL |
| 0040 | 24 | | GK | | 38-0 | 30-31-12 | D03566 | | 6 | | | D40594P | | 12 | | ALL |
| 0041 | 22 | | GA | | 41-0 | 22-21-21 | D41862P | | 1 | | | TB0113X | A001 | BJ | | ALL |
| 0042 | 22 | | GA | | 42-0 | 22-21-21 | D41862P | | 2 | | | D03513 | | 5 | | 001-099 |
| 0042 | 22 | | GA | | 41-0 | 22-21-21 | D41862P | | 2 | | | D03513 | | 5 | | 115-199 |
| 0043 | 22 | | GA | | 42-0 | 22-21-21 | D41862P | | 3 | | | D03513 | | 7 | | 001-099 |
| 0043 | 22 | | GA | | 41-0 | 22-21-21 | D41862P | | 3 | | | D03513 | | 7 | | 115-199 |
| 0044 | 22 | | GA | | 41-0 | 27-61-12 | D41862P | | 4 | | | D03566 | | 17 | | ALL |
| 0045 | 22 | | GA | | 5-0 | 22-21-21 | TB0113X | D016 | BJ | | | D03513 | | 6 | | 001-099 |
| 0045 | 22 | | GA | | 4-0 | 22-21-21 | TB0113X | D016 | BJ | | | D03513 | | 6 | | 115-199 |
| 0046 | 22 | | GA | | 5-0 | 22-21-21 | GD00598 | DC.. | 2 | | | D03513 | | 12 | | ALL |
| 0047 | 22 | | GA | | 41-0 | 30-11-11 | D41842P | | 1 | | | TB0113Y | C004 | BJ | | 115-199 |
| 0048 | 22 | | GA | | 41-0 | 30-11-11 | D41842P | | 2 | | | TB0113Y | A004 | BJ | | 115-199 |
| 0050 | 22 | | GA | | 10-0 | 30-43-11 | D40804J | | 14 | | | TB0113X | B011 | BJ | | ALL |
| 0051 | 22 | | GA | | 41-0 | 30-41-12 | D03554 | | 9 | | | D41842P | | 3 | | 001-099 |
| 0051 | 22 | | GA | | 40-0 | 30-41-12 | D03554 | | 9 | | | D41842P | | 3 | | 115-199 |
| 0052 | 22 | | GA | | 41-0 | 30-41-12 | D03554 | | 8 | | | D41842P | | 4 | | 001-099 |
| 0052 | 22 | | GA | | 40-0 | 30-41-12 | D03554 | | 8 | | | D41842P | | 4 | | 115-199 |
| 0053 | 22 | | GA | | 37-0 | 30-41-12 | TB0113X | A011 | BJ | | | D41872P | | 5 | | 001-099 |
| 0053 | 22 | | GA | | 36-0 | 30-41-12 | TB0113X | A011 | BJ | | | D41872P | | 5 | | 115-199 |
| 0063 | 24 | | GK | | 46-0 | 52-71-11 | D03566 | | 9 | | | D40924P | | 2 | | ALL |
| 0064 | 24 | | GK | | 46-0 | 52-71-11 | D03566 | | 10 | | | D40924P | | 3 | | ALL |
| 0065 | 24 | | GK | | 46-0 | 52-71-11 | D03566 | | 11 | | | D40924P | | 4 | | ALL |
| 0066 | 24 | | GK | | 46-0 | 52-71-11 | D03566 | | 8 | | | D40924P | | 1 | | 001-099 |
| 0066 | 24 | | GK | | 45-0 | 52-71-11 | D03566 | | 8 | | | D40924P | | 1 | | 115-199 |
| 0067 | 22 | | GA | | 38-0 | 30-41-11 | D41872P | | 6 | | | TB0111X | B002 | BJ | | ALL |
| 0068 | 20 | | GA | | 39-0 | 33-41-11 | D03507 | | 9 | | | D40594P | | 3 | | ALL |
| 0069 | 20 | | GA | | 11-0 | 33-41-11 | D03507 | | 7 | | | D40804J | | 2 | | ALL |
| 0070 | 20 | | GA | | 11-0 | 33-42-12 | D40804J | | 13 | | | D03507 | | 13 | | 115-199 |
| 0071 | 20 | | GA | | 11-0 | 33-42-12 | D40804J | | 11 | | | D03507 | | 11 | | ALL |
| 0072 | 20 | | GA | | 44-0 | 33-42-12 | D41848P | | 1 | | | D03507 | | 10 | | ALL |
| 0073 | 20 | | GA | | 44-0 | 33-42-12 | D41848P | | 2 | | | D03507 | | 14 | | 115-199 |
| 0074 | 24 | | GK | | 22-0 | SPARE | D41842P | | 7 | | | D40594P | | 51 | | ALL |
| 0075 | 20 | | GA | | 11-0 | 33-43-11 | D40804J | | 12 | | | D03507 | | 19 | | 001-099 |
| 0075 | 20 | | GA | | 11-0 | 33-43-11 | D40804J | | 12 | | | D03507 | | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 22

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2072 | 286N2072 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0076 | 20 | | GA | | 39-0 | 33-43-11 | D40594P | | 52 | | D03507 | | 18 | | 001-099 |
| 0076 | 20 | | GA | | 39-0 | 33-43-11 | D40594P | | 52 | | D03507 | | 1 | | 115-199 |
| 0079 | 22 | | GA | | 5-0 | 30-41-12 | D03554 | | 6 | | GD00610 | AC.. | 2 | | 001-099 |
| 0079 | 20 | | GA | | 4-0 | 30-41-12 | D03554 | | 6 | | GD00610 | AC.. | 2 | | 115-199 |
| 0080 | 22 | | GA | | 5-0 | 30-41-12 | D03554 | | 5 | | GD00610 | AC.. | 2 | | 001-099 |
| 0080 | 20 | | GA | | 4-0 | 30-41-12 | D03554 | | 5 | | GD00610 | AC.. | 2 | | 115-199 |
| 0086 | 22 | | GA | | 6-0 | 33-16-32 | D03566 | | 3 | | TB0114Z | | 2 | BJ | ALL |
| 0088 | 22 | | GA | | 6-0 | 33-16-42 | D03566 | | 4 | | TB0114Z | | 17 | BJ | ALL |
| 0089 | 22 | | GA | | 6-0 | 33-16-42 | D03566 | | 13 | | TB0114Z | | 19 | BJ | ALL |
| 0090 | 22 | | GA | | 5-0 | 33-16-42 | D03554 | | 4 | | TB0114Z | | 18 | BJ | ALL |
| 0091 | 22 | | GA | | 5-0 | 33-16-42 | D03554 | | 3 | | TB0114Z | | 19 | BJ | ALL |
| 0098 | 20 | | GA | | 5-0 | 33-13-31 | D03517 | | 1 | | TB0114Z | | 8 | BJ | ALL |
| 0099 | 20 | | GA | | 5-0 | 33-13-31 | D03517 | | 2 | | TB0114Z | | 10 | BJ | ALL |
| 0102 | 20 | | GA | | 31-0 | 23-31-13 | D41848P | | 7 | | D40924P | | 5 | | 001-099 |
| 0102 | 20 | | GA | | 32-0 | 23-31-13 | D41848P | | 7 | | D40924P | | 5 | | 115-199 |
| 0103 | 20 | | GA | | 31-0 | 23-31-13 | D41848P | | 8 | | D40924P | | 6 | | 001-099 |
| 0103 | 20 | | GA | | 32-0 | 23-31-13 | D41848P | | 8 | | D40924P | | 6 | | 115-199 |
| 0104 | 20 | | GA | | 34-0 | 36-11-21 | D40804J | | 32 | | D40594P | | 13 | | ALL |
| 0109 | 20 | | GA | | 9-0 | SPARE | D41862P | | 5 | | D41842P | | 10 | | 115-199 |
| 0110 | 20 | | GA | | 9-0 | SPARE | D41862P | | 6 | | D41842P | | 11 | | 115-199 |
| 0111 | 20 | | GA | | 22-0 | SPARE | D40594P | | 14 | | D41842P | | 12 | | 115-199 |
| 0112 | 20 | | GA | | 9-0 | SPARE | D41862P | | 15 | | D41842P | | 13 | | 115-199 |
| 0113 | 20 | | GA | | 22-0 | SPARE | D40594P | | 16 | | D41842P | | 14 | | 115-199 |
| 0114 | 20 | | GA | | 22-0 | SPARE | D40594P | | 17 | | D41842P | | 15 | | 115-199 |
| 0115 | 20 | | GA | | 23-0 | SPARE | D41872P | | 7 | | D41842P | | 16 | | 115-199 |
| 0116 | 20 | | GA | | 23-0 | SPARE | D41872P | | 8 | | D41842P | | 17 | | 115-199 |
| 0117 | 20 | | GA | | 24-0 | SPARE | D41872P | | 9 | | D41848P | | 9 | | ALL |
| 0118 | 20 | | GA | | 24-0 | SPARE | D41872P | | 10 | | D41848P | | 10 | | ALL |
| 0119 | 20 | | GA | | 24-0 | SPARE | D41872P | | 11 | | D41848P | | 11 | | 115-199 |
| 0120 | 20 | | GA | | 24-0 | SPARE | D41872P | | 12 | | D41848P | | 12 | | 115-199 |
| 0121 | 20 | | GA | | 39-0 | SPARE | D03513 | CAP | Y | | D40594P | | 30 | | 001-099 |
| 0121 | 20 | | GA | | 38-0 | SPARE | D03513 | CAP | Y | | D40594P | | 30 | | 115-199 |
| 0122 | 20 | | GA | | 39-0 | SPARE | D03513 | CAP | Y | | D40594P | | 31 | | 001-099 |
| 0122 | 20 | | GA | | 38-0 | SPARE | D03513 | CAP | Y | | D40594P | | 31 | | 115-199 |
| 0123 | 20 | | GA | | 38-0 | SPARE | D03513 | CAP | Y | | D40594P | | 32 | | 115-199 |
| 0124 | 20 | | GA | | 38-0 | SPARE | D03513 | CAP | Y | | D40594P | | 33 | | 115-199 |
| 0130 | 20 | | GA | | 39-0 | SPARE | D03507 | CAP | Y | | D40594P | | 19 | | 001-099 |
| 0131 | 20 | | GA | | 34-0 | SPARE | D40804J | | 36 | | D40594P | | 37 | | 001-099 |
| 0131 | 22 | | GA | | 34-0 | SPARE | D40804J | | 36 | | D40594P | | 37 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 23

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2072 | 286N2072 | | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0132 | 22 | GA | | | 38-0 | SPARE | | D03513 | | 14 | | D40594P | | 45 | | 115-199 |
| 0133 | 22 | GA | | | 38-0 | SPARE | | D03513 | | 13 | | D40594P | | 39 | | 115-199 |
| 0134 | 22 | GA | | | 38-0 | SPARE | | D03513 | | 2 | | D40594P | | 40 | | 115-199 |
| 0135 | 22 | GA | | | 38-0 | SPARE | | D03513 | | 1 | | D40594P | | 41 | | 115-199 |
| 0136 | 22 | GA | | | 38-0 | SPARE | | D03513 | | 15 | | D40594P | | 43 | | 115-199 |
| 0151 | 24 | GK | | | 8-0 | 21-61-21 | | D40804J | | 38 | | TB0114X | C023 | BJ | | ALL |
| 0152 | 20 | GA | | | 8-0 | 33-43-12 | | D40804J | | 7 | | TB0114X | A024 | BJ | | ALL |
| 0153 | 24 | GK | | | 26-0 | SPARE | | D40594P | | 20 | | D40924P | | 7 | | 001-099 |
| 0154 | 24 | GK | | | 12-0 | 24-51-31 | | D40804J | | 45 | | TB0111A | A007 | 2 | | 001-099 |
| 0155 | 24 | GK | | | 1-0 | 24-51-31 | | TB0111A | C003 | 2 | | TB0111A | C007 | 2 | | 001-099 |
| 0156 | 24 | GK | | | 2-0 | 24-51-31 | | TB0111A | C008 | 2 | | TB0111A | C007 | 2 | | 001-099 |
| 0157 | 24 | GK | | | 10-0 | 24-51-31 | | TB0111A | C008 | 2 | | TB5006 | | 1 | E | 001-099 |
| 0158 | 24 | GK | | | 8-0 | 26-11-11 | | D40804J | | 27 | | TB0112A | A023 | 2 | | 001-099 |
| 0159 | 24 | GK | | | 8-0 | 26-11-21 | | D40804J | | 16 | | TB0112A | A021 | 2 | | 001-099 |
| 0160 | 24 | GK | | | 1-0 | 26-11-21 | | TB0112A | C022 | 2 | | TB0112A | C021 | 2 | | 001-099 |
| 0161 | 24 | GK | | | 8-0 | 26-15-11 | | D40804J | | 17 | | TB0112A | A019 | 2 | | 001-099 |
| 0162 | 24 | GK | | | 2-0 | 26-15-11 | | TB0112A | C020 | 2 | | TB0112A | C019 | 2 | | 001-099 |
| 0163 | 24 | GK | | | 8-0 | 26-16-11 | | D40804J | | 18 | | TB0112A | A017 | 2 | | 001-099 |
| 0228 | 20 | GA | | | 8-0 | 25-31-21 | | D40804J | | 9 | | TB0114X | A013 | BJ | | 115-199 |
| 0230 | 24 | GK | | | 8-0 | 33-11-11 | | D40804J | | 22 | | TB0114X | A023 | BJ | | ALL |
| 0233 | 24 | GK | | | 8-0 | 21-44-11 | | D40804J | | 28 | | TB0114X | D014 | BJ | | ALL |
| 0238 | 22 | GA | | | 7-0 | 33-16-32 | | D03513 | | 3 | | TB0114Z | | 2 | BJ | ALL |
| 0239 | 24 | GK | | | 12-0 | 21-61-31 | | D40804J | | 21 | | TB0111X | C001 | BJ | | 001-099 |
| 0239 | 24 | GK | | | 11-0 | 21-61-31 | | D40804J | | 21 | | TB0111X | C001 | BJ | | 115-199 |
| 0240 | 20 | GA | | | 10-0 | 21-31-21 | | D40804J | | 25 | | TB0113X | A016 | BJ | | ALL |
| 0243 | 22 | GA | | | 34-0 | 29-11-21 | | D40804J | | 33 | | D40594P | | 15 | | ALL |
| 0244 | 20 | GA | | | 10-0 | 24-51-24 | | D40804J | | 35 | | TB0113X | C016 | BJ | | ALL |
| 0245 | 20 | GA | | | 6-0 | 21-61-11 | | D04350 | | 3 | | GD00598 | ST.. | 2 | | 001-099 |
| 0245 | 20 | GA | | | 8-0 | 21-61-11 | | D04350 | | 3 | | GD00598 | ST.. | 2 | | 115-199 |
| 0246 | 24 | GK | | | 6-0 | 21-61-11 | | D04350 | | 2 | | GD00598 | AC.. | 2 | | 001-099 |
| 0246 | 24 | GK | | | 8-0 | 21-61-11 | | D04350 | | 2 | | GD00598 | AC.. | 2 | | 115-199 |
| 0247 | 24 | GK | | | 12-0 | 21-61-11 | | D04350 | | 1 | | D40804J | | 37 | | ALL |
| 0248 | 22 | GA | | | 8-0 | 24-51-72 | | D40804J | | 30 | | TB0116X | B017 | BJ | | ALL |
| 0249 | 24 | GK | | | 8-0 | 33-11-61 | | D40804J | | 40 | | TB0116X | B018 | BJ | | ALL |
| 0250 | 24 | GK | | | 41-0 | 33-24-11 | | D41848P | | 13 | | TB0112X | C003 | BJ | | ALL |
| 0251 | 22 | GA | | | 34-0 | 28-22-11 | | D40804J | | 10 | | D40594P | | 46 | | ALL |
| 0252 | 18 | GA | | | 8-0 | 73-21-21 | | D40804J | | 8 | 18 | TB0114F | A005 | 2 | | 001-099 |
| 0252 | 18 | GA | | | 26-0 | 73-21-21 | | D40804J | | 8 | 18 | TB0101F | A005 | 2 | | 115-199 |
| 0253 | 18 | GA | | | 8-0 | 73-21-22 | | D40804J | | 41 | 18 | TB0114F | C005 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 24

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|-------------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2072 | 286N2072 | | | FLIGHT DECK TO E/E BAY CAT "R2" SYSTEM (continued) | | | | | | | | | | | |
| 0253 | 18 | | GA | | 26-0 | 73-21-22 | D40804J | 41 | 18 | | TB0101F | C005 | 2 | | 115-199 |
| 0561 | 24 | | GK | | 12-0 | 33-11-21 | D40804J | 43 | | | TB0115X | D015 | BJ | | ALL |
| 0800 | 20 | | GA | | 15-0 | 33-14-51 | D40804J | 6 | | | TB5044 | 1 | C | | 115-199 |
| 0802 | 20 | | GA | | 18-0 | 33-14-51 | TB5044 | 2 | C | | GD00610 | DC.. | 2 | | 115-199 |
| 2001B | 24 | | GL | AA | 40-0 | 21-61-11 | D02554 | 2 | | | D40594P | 28 | | | ALL |
| 2001R | 24 | | GL | AA | 0-0 | 21-61-11 | D02554 | 1 | | | D40594P | 29 | | | ALL |
| 2003B | 24 | | GL | BO | 40-0 | 21-61-11 | D40594P | 21 | | | D02554 | 4 | | | 001-099 |
| 2003B | 24 | | GL | AB | 40-0 | 21-61-11 | D40594P | 21 | | | D02554 | 4 | | | 115-199 |
| 2003R | 24 | | GL | BO | 0-0 | 21-61-11 | D40594P | 22 | | | D02554 | 3 | | | 001-099 |
| 2003R | 24 | | GL | AB | 0-0 | 21-61-11 | D40594P | 22 | | | D02554 | 3 | | | 115-199 |
| W2073 | 286N2073 | | | VHF-R CONTROL, P8 TO E4-3 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 33-13-52 | D00127 | 1 | | | TB0058Z | 3 | BJ | | 001-099 |
| 0001 | 20 | | GA | | 6-0 | 33-13-52 | D00127 | 1 | | | TB0058Z | 3 | BJ | | 115-199 |
| 0002 | 20 | | GA | | 5-0 | 33-13-52 | D00127 | 2 | | | GD00742 | AC.. | 2 | | 001-099 |
| 0002 | 20 | | GA | | 6-0 | 33-13-52 | D00127 | 2 | | | GD00742 | AC.. | 2 | | 115-199 |
| 0003 | 18 | | GA | | 41-0 | 23-12-21 | D00127 | 13 | 18 | | D41533P | 7 | 18 | | 001-099 |
| 0003 | 18 | | GA | | 41-0 | 23-12-21 | D00127 | 13 | 18 | | D41533P | 7 | | | 115-199 |
| 0005 | 24 | | GK | | 41-0 | 23-12-21 | D00127 | 5 | | | D41533P | 5 | | | ALL |
| 0006 | 24 | | GK | | 41-0 | 23-12-21 | D00127 | 6 | | | D41533P | 6 | | | ALL |
| 0007 | 24 | | GK | | 41-0 | 23-12-21 | D00127 | 7 | | | D41533P | 1 | | | ALL |
| 0008 | 24 | | GK | | 41-0 | 23-12-21 | D00127 | 8 | | | D41533P | 8 | | | ALL |
| 0009 | 24 | | GK | | 41-0 | 23-12-21 | D00127 | 9 | | | D41533P | 9 | | | ALL |
| 0010 | 20 | | GA | | 5-0 | 23-12-21 | D00127 | 14 | | | GD01650 | DC.. | 2 | | 001-099 |
| 0010 | 20 | | GA | | 6-0 | 23-12-21 | D00127 | 14 | | | GD01650 | DC.. | 2 | | 115-199 |
| 5001B | 24 | | G2 | AA | 41-0 | 23-12-21 | D00127 | 18 | | | D41533P | 12 | | | ALL |
| 5001R | 24 | | G2 | AA | 0-0 | 23-12-21 | D00127 | 17 | | | D41533P | 11 | | | ALL |
| 5001Z | | | | AA | 0-0 | 23-12-21 | D00127 | 19 | | | D41533P | 3 | | | ALL |
| W2075 | 286N2075 | | | TRANSPONDER SYSTEM-L, P8 TO E3-3 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 33-13-52 | D00255 | 1 | | | TB0059Z | 2 | BJ | | ALL |
| 0002 | 20 | | GA | | 5-0 | 33-13-52 | D00255 | 2 | | | GD00082 | AC.. | 2 | | ALL |
| 0003 | 22 | | GA | | 5-0 | 34-53-11 | D00255 | 3 | | | TB0059Y | A011 | BJ | | ALL |
| 0004 | 20 | | GA | | 5-0 | 34-53-11 | D00255 | 4 | | | GD00082 | AC.. | 2 | | ALL |
| 0005 | 22 | | GA | | 39-0 | 34-53-11 | D00255 | 5 | | | D41525P | 5 | | | 001-099 |
| 0005 | 22 | | GA | | 38-0 | 34-53-11 | TB0059Y | A011 | BJ | | D41525P | 5 | | | 115-199 |
| 0006 | 20 | | GA | | 5-0 | 34-53-11 | D00255 | 6 | | | GD00082 | DC.. | 2 | | 001-099 |
| 0006 | 20 | | GA | | 5-0 | 34-53-11 | D00255 | 8 | | | GD00082 | DC.. | 2 | | 115-199 |
| 0007 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | 7 | | | D41525P | 7 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 25

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|------|---------|--------|-------------|----|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2075 | 286N2075 | | | | TRANSPONDER SYSTEM-L, P8 TO E3-3 (continued) | | | | | | | | | | | | |
| 0008 | 20 | | GA | | 5-0 | 34-53-11 | D00255 | | | | 8 | | GD00082 | DC.. | 2 | | 001-099 |
| 0008 | 24 | | GK | | 38-0 | 34-53-11 | D00255 | | | | 9 | | D41525P | | 9 | | 115-199 |
| 0009 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 9 | | D41525P | | 9 | | 001-099 |
| 0009 | 24 | | GK | | 38-0 | SPARE | D00255 | | | | 19 | | D41525P | | 1 | | 115-199 |
| 0010 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 10 | | D41525P | | 10 | | 001-099 |
| 0010 | 24 | | GK | | 38-0 | 34-53-11 | D00255 | | | | 20 | | D41525P | | 2 | | 115-199 |
| 0011 | 22 | | GA | | 6-0 | 33-16-61 | D00255 | | | | 18 | | TB0058Z | | 4 | BJ | 001-099 |
| 0011 | 22 | | GA | | 5-0 | 33-16-11 | D00255 | | | | 18 | | TB0059X | A003 | | BJ | 115-199 |
| 0012 | 22 | | GA | | 20-0 | 33-16-51 | D00255 | | | | 21 | | TB0100Y | A010 | | BJ | 001-099 |
| 0012 | 22 | | GA | | 5-0 | 33-16-11 | D00255 | | | | 21 | | TB0059X | B003 | | BJ | 115-199 |
| 0013 | 24 | | GK | | 38-0 | 34-53-11 | D00255 | | | | 10 | | D41525P | | 8 | | 115-199 |
| 0015 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 15 | | D41525P | | 15 | | 001-099 |
| 0015 | 24 | | GK | | 38-0 | 34-53-11 | D00255 | | | | 15 | | D41525P | | 3 | | 115-199 |
| 0016 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 16 | | D41525P | | 16 | | 001-099 |
| 0017 | 22 | | GA | | 39-0 | 34-53-11 | D00255 | | | | 17 | | D41525P | | 17 | | 001-099 |
| 0017 | 24 | | GK | | 38-0 | 34-53-11 | D00255 | | | | 7 | | D41525P | | 4 | | 115-199 |
| 0019 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 19 | | D41525P | | 19 | | 001-099 |
| 0020 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 20 | | D41525P | | 20 | | 001-099 |
| 0024 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 24 | | D41525P | | 24 | | 001-099 |
| 0024 | 24 | | GK | | 38-0 | 34-53-11 | D00255 | | | | 24 | | D41525P | | 12 | | 115-199 |
| 0060 | 20 | | GA | | 6-0 | 34-53-11 | D00255 | | | | 6 | | GD00082 | DC.. | 2 | | 115-199 |
| 0100 | 20 | | GA | | 5-0 | 34-53-11 | D00255 | | | | | AB | GD00082 | ST.. | 2 | | 001-099 |
| 0100 | 22 | | GA | | 6-0 | 34-53-11 | D00255 | | | | | FA | GD00082 | ST.. | 2 | | 115-199 |
| 0111 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 11 | | D41525P | | 11 | | 001-099 |
| 0112 | 24 | | GK | | 39-0 | 34-53-11 | D00255 | | | | 12 | | D41525P | | 12 | | 001-099 |
| 0113 | 22 | | GA | | 39-0 | 34-53-11 | D41525P | | | | 13 | | TB0059Y | A011 | | BJ | 001-099 |
| 5001B | 24 | | G2 | AA | 39-0 | 34-53-11 | D00255 | | | | 23 | | D41525P | | 23 | | 001-099 |
| 5001B | 24 | | G2 | AZ | 38-0 | 34-53-11 | D00255 | | | | 23 | | D41525P | | 11 | | 115-199 |
| 5001R | 24 | | G2 | AA | 0-0 | 34-53-11 | D00255 | | | | 22 | | D41525P | | 22 | | 001-099 |
| 5001R | 24 | | G2 | AZ | 0-0 | 34-53-11 | D00255 | | | | 22 | | D41525P | | 10 | | 115-199 |
| 5001Z | | | | AA | 0-0 | 34-53-11 | D00255 | | | | | AB | D41525P | | 21 | | 001-099 |
| 5001Z | | | | AZ | 0-0 | 34-53-11 | D00255 | | | | | FA | D41525P | | 13 | | 115-199 |
| W2077 | 286N2077 | | | | TRANSPONDER SYSTEM-R, P8 TO E3-2 | | | | | | | | | | | | |
| 0003 | 22 | | GA | | 6-0 | 34-53-21 | D00257 | | | | 3 | | TB0058Y | C013 | | BJ | 001-099 |
| 0003 | 22 | | GA | | 5-0 | 34-53-21 | D00257 | | | | 3 | | TB0058Y | C013 | | BJ | 115-199 |
| 0004 | 20 | | GA | | 7-0 | 34-53-21 | D00257 | | | | 4 | | GD01650 | AC.. | 2 | | 001-099 |
| 0004 | 20 | | GA | | 5-0 | 34-53-21 | D00257 | | | | 4 | | GD01650 | AC.. | 2 | | 115-199 |
| 0005 | 22 | | GA | | 41-0 | 34-53-21 | D00257 | | | | 5 | | SM00001 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 26

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|--------|-------|------|---------|--------|----|-------------|---------|
| | GA | CO | TY | | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2077 | 286N2077 | | | | TRANSPONDER SYSTEM-R, P8 TO E3-2 (continued) | | | | | | | | | | | |
| 0006 | 20 | | GA | | 6-0 | 34-53-21 | D00257 | | 6 | | | GD01650 | DC.. | 2 | *1 | 001-099 |
| 0006 | 20 | | GA | | 5-0 | 34-53-21 | D00257 | | 8 | | | GD01650 | DC.. | 2 | *2 | 115-199 |
| 0007 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 7 | | | D41527P | | 7 | | 001-099 |
| 0007 | 22 | | GA | | 45-0 | SPARE | D00257 | | 17 | | | D41527P | | 7 | | 115-199 |
| 0008 | 20 | | GA | | 6-0 | 34-53-21 | D00257 | | 8 | | | GD01650 | DC.. | 2 | *1 | 001-099 |
| 0008 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 9 | | | D41527P | | 9 | | 115-199 |
| 0009 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 9 | | | D41527P | | 9 | | 001-099 |
| 0009 | 24 | | GK | | 45-0 | SPARE | D00257 | | 19 | | | D41527P | | 1 | | 115-199 |
| 0010 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 10 | | | D41527P | | 10 | | 001-099 |
| 0010 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 20 | | | D41527P | | 2 | | 115-199 |
| 0011 | 22 | | GA | | 5-0 | 33-16-41 | D00257 | | 18 | | | TB0058X | A001 | BJ | | 115-199 |
| 0012 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 12 | | | D41527P | | 12 | | 001-099 |
| 0013 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 10 | | | D41527P | | 13 | | 115-199 |
| 0015 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 15 | | | D41527P | | 15 | | 001-099 |
| 0015 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 15 | | | D41527P | | 3 | | 115-199 |
| 0016 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 16 | | | D41527P | | 16 | | 001-099 |
| 0016 | 20 | | GA | | 5-0 | 34-53-21 | D00257 | | 6 | | | GD01650 | DC.. | 2 | *2 | 115-199 |
| 0017 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 17 | | | D41527P | | 17 | | 001-099 |
| 0017 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 7 | | | D41527P | | 12 | | 115-199 |
| 0019 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 19 | | | D41527P | | 19 | | 001-099 |
| 0020 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 20 | | | D41527P | | 20 | | 001-099 |
| 0024 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 24 | | | D41527P | | 24 | | 001-099 |
| 0024 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 24 | | | D41527P | | 4 | | 115-199 |
| 0025 | 22 | | GA | | 45-0 | 34-53-21 | D41527P | | 5 | | | TB0058Y | C013 | BJ | | 001-099 |
| 0025 | 22 | | GA | | 46-0 | 34-53-21 | D41527P | | 5 | | | TB0058Y | C013 | BJ | | 115-199 |
| 0026 | 20 | | GA | | 5-0 | 34-53-21 | D41527P | | 13 | | | SM00003 | | 9 | | 001-099 |
| 0026 | 20 | | GA | | 5-0 | 34-53-21 | D41527P | | 6 | | | SM00003 | | 9 | | 115-199 |
| 0029 | 22 | | GA | | 5-0 | 34-53-11 | D01427 | | A | | | SP27001 | | 9 | | ALL |
| 0030 | 20 | | GA | | 3-0 | 34-53-11 | D01427 | | B | | | SM00003 | | 9 | | 001-099 |
| 0030 | 20 | | GA | | 2-0 | 34-53-11 | D01427 | | B | | | SM00003 | | 9 | | 115-199 |
| 0031 | 24 | | GK | | 3-0 | 34-53-11 | D01427 | | C | | | SM00001 | | 9 | | 001-099 |
| 0031 | 24 | | GK | | 2-0 | 34-53-11 | D01427 | | C | | | SM00001 | | 9 | | 115-199 |
| 0032 | 22 | | GA | | 5-0 | 34-53-11 | D01435 | | A | | | SP27001 | | 9 | | ALL |
| 0033 | 20 | | GA | | 3-0 | 34-53-11 | D01435 | | B | | | SM00003 | | 9 | | ALL |
| 0034 | 24 | | GK | | 3-0 | 34-53-11 | D01435 | | C | | | SM00001 | | 9 | | ALL |
| 0100 | 20 | | GA | | 6-0 | 34-53-21 | D00257 | | | | AA | GD01650 | ST.. | 2 | | 001-099 |
| 0100 | 20 | | GA | | 6-0 | 34-53-21 | D00257 | | | | FA | GD01650 | ST.. | 2 | | 115-199 |
| 0111 | 24 | | GK | | 45-0 | 34-53-21 | D00257 | | 11 | | | D41527P | | 11 | | 001-099 |
| 5001B | 24 | | G2 | AA | 45-0 | 34-53-21 | D00257 | | 23 | | | D41527P | | 23 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 27

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2077 | 286N2077 | | | TRANSPONDER SYSTEM-R, P8 TO E3-2 (continued) | | | | | | | | | | | |
| 5001B | 24 | G2 | AZ | | 45-0 | 34-53-21 | D00257 | 23 | | | D41527P | 11 | | | 115-199 |
| 5001R | 24 | G2 | AA | | 0-0 | 34-53-21 | D00257 | 22 | | | D41527P | 22 | | | 001-099 |
| 5001R | 24 | G2 | AZ | | 0-0 | 34-53-21 | D00257 | 22 | | | D41527P | 10 | | | 115-199 |
| 5001Z | | | AA | | 0-0 | 34-53-21 | D00257 | | | AA | D41527P | 21 | | | 001-099 |
| 5001Z | | | AZ | | 0-0 | 34-53-21 | D00257 | | | FA | D41527P | 14 | | | 115-199 |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM | | | | | | | | | | | |
| 0001 | 24 | GK | | | 40-0 | 36-11-41 | D03542 | 3 | | | D40570P | 55 | | | 001-099 |
| 0001 | 24 | GK | | | 40-0 | 36-11-41 | D03542 | 3 | | | D40570P | 12 | | | 115-199 |
| 0002 | 24 | GK | | | 39-0 | 36-11-41 | D40570P | 23 | | | TB0113X | A019 | BJ | | 001-099 |
| 0002 | 24 | GK | | | 38-0 | 36-11-41 | D40570P | 9 | | | TB0058X | A002 | BJ | | 115-199 |
| 0004 | 20 | GA | | | 30-0 | 21-31-31 | SP00496 | | 9 | | D02346 | 2 | | | 001-099 |
| 0004 | 20 | GA | | | 31-0 | 21-31-31 | SP00496 | | 9 | | D02346 | 2 | | | 115-199 |
| 0005 | 20 | GA | | | 30-0 | 21-31-31 | SP00498 | | 9 | | D02346 | 3 | | | 001-099 |
| 0005 | 20 | GA | | | 31-0 | 21-31-31 | SP00498 | | 9 | | D02346 | 3 | | | 115-199 |
| 0006 | 16 | GA | | | 41-0 | 24-11-11 | D03504 | 6 | | | D41850P | 49 | 16 | | ALL |
| 0007 | 16 | GA | | | 40-0 | 24-11-21 | D03504 | 10 | | | D40570P | 41 | 16 | | 001-099 |
| 0007 | 16 | GA | | | 41-0 | 24-11-21 | D03504 | 10 | | | D40570P | 41 | 16 | | 115-199 |
| 0010 | 24 | GK | | | 12-0 | 33-11-11 | TB0114X | A023 | BJ | | D41010P | 23 | | | ALL |
| 0011 | 22 | GA | | | 15-0 | 33-16-51 | D41174J | 6 | | | SM00008 | | 9 | | ALL |
| 0012 | 24 | GK | | | 14-0 | 33-11-11 | D40806J | 2 | | | SM00002 | | 9 | | ALL |
| 0013 | 24 | GK | | | 36-0 | 36-11-41 | D40570P | 1 | | | TB0058X | D001 | BJ | | 001-099 |
| 0013 | 24 | GK | | | 38-0 | 36-11-41 | D40570P | 1 | | | TB0058X | D001 | BJ | | 115-199 |
| 0014Y | 20 | QB | | | 29-0 | 27-41-21 | D40806J | 21 | | | TB0100X | B004 | BJ | | 001-099 |
| 0014Y | 20 | QB | | | 30-0 | 27-41-21 | D40806J | 21 | | | TB0100X | B004 | BJ | | 115-199 |
| 0015 | 24 | GK | | | 34-0 | 34-33-31 | D40570P | 5 | | | D03706 | CAP | Y | | 001-099 |
| 0015 | 24 | GK | | | 34-0 | 34-33-31 | D03706 | | CAP | Y | D40570P | 5 | | | 115-199 |
| 0016 | 20 | GA | | | 8-0 | 74-31-21 | D40806J | 11 | | | TB0114X | D013 | BJ | | 001-099 |
| 0016 | 20 | GA | | | 8-0 | 74-31-11 | D40806J | 8 | | | TB0116X | D011 | BJ | | 115-199 |
| 0017 | 20 | GA | | | 40-0 | 74-31-21 | D03528 | 6 | | | D40570P | 47 | | | 001-099 |
| 0017 | 20 | GA | | | 41-0 | 74-31-21 | D03528 | 6 | | | D40570P | 47 | | | 115-199 |
| 0018 | 22 | GA | | | 5-0 | 49-61-11 | D03508 | 8 | | | GD00600 | DC.. | 2 | | 001-099 |
| 0018 | 22 | GA | | | 4-0 | 49-61-11 | D03508 | 8 | | | GD00600 | DC.. | 2 | | 115-199 |
| 0019 | 22 | GA | | | 7-0 | 49-61-11 | D03508 | 15 | | | TB0115X | D001 | BJ | | ALL |
| 0020 | 20 | GA | | | 40-0 | 74-31-21 | D03528 | 5 | | | D40570P | 48 | | | 001-099 |
| 0020 | 20 | GA | | | 41-0 | 74-31-21 | D03528 | 5 | | | D40570P | 48 | | | 115-199 |
| 0021 | 22 | GA | | | 14-0 | 30-21-11 | D03528 | 11 | | | SM00025 | | 9 | | ALL |
| 0022 | 20 | GA | | | 5-0 | 30-21-11 | D03528 | 12 | | | GD00600 | DC.. | 2 | | 001-099 |
| 0022 | 20 | GA | | | 4-0 | 30-21-11 | D03528 | 12 | | | GD00600 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 28

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0023 | 24 | | GK | | 27-0 | 33-11-21 | TB0115X | D016 | BJ | | D41174J | 32 | | | 001-099 |
| 0023 | 24 | | GK | | 28-0 | 33-11-21 | TB0115X | D016 | BJ | | D41174J | 32 | | | 115-199 |
| 0024 | 22 | | GA | | 46-0 | 29-11-31 | D03548 | 2 | | | D41844P | 12 | | | 001-099 |
| 0024 | 22 | | GA | | 45-0 | 29-11-31 | D03548 | 2 | | | D41844P | 12 | | | 115-199 |
| 0025 | 22 | | GA | | 46-0 | 29-11-31 | D03548 | 1 | | | D41844P | 13 | | | 001-099 |
| 0025 | 22 | | GA | | 45-0 | 29-11-31 | D03548 | 1 | | | D41844P | 13 | | | 115-199 |
| 0026 | 22 | | GA | | 22-0 | SPARE | D40570P | 2 | | | D41414P | 3 | | | 001-099 |
| 0026 | 22 | | GA | | 24-0 | 29-22-11 | D40570P | 2 | | | D41414P | 3 | | | 115-199 |
| 0027 | 24 | | GK | | 17-0 | 33-11-11 | D41174J | 1 | | | TB0121X | D006 | BJ | | ALL |
| 0028 | 22 | | GA | | 22-0 | 29-22-11 | D40570P | 4 | | | D41414P | 5 | | | 001-099 |
| 0028 | 22 | | GA | | 24-0 | 29-22-11 | D40570P | 4 | | | D41414P | 5 | | | 115-199 |
| 0029 | 22 | | GA | | 36-0 | 33-16-51 | D41008P | 18 | | | D40600P | 6 | | | ALL |
| 0030 | 22 | | GA | | 17-0 | 33-16-51 | SM00006 | | 9 | | TB0100Y | A009 | BJ | | 001-099 |
| 0030 | 22 | | GA | | 18-0 | 33-16-51 | SM00006 | | 9 | | TB0100Y | A009 | BJ | | 115-199 |
| 0031 | 22 | | GA | | 17-0 | 33-16-51 | SM00007 | | 9 | | TB0100Y | A010 | BJ | | 001-099 |
| 0031 | 22 | | GA | | 18-0 | 33-16-51 | SM00007 | | 9 | | TB0100Y | A010 | BJ | | 115-199 |
| 0032 | 22 | | GA | | 17-0 | 33-16-51 | SM00008 | | 9 | | TB0100X | D001 | BJ | | 001-099 |
| 0032 | 22 | | GA | | 18-0 | 33-16-51 | SM00008 | | 9 | | TB0100X | D001 | BJ | | 115-199 |
| 0033 | 22 | | GA | | 17-0 | 33-16-51 | SM00009 | | 9 | | TB0100Y | C009 | BJ | | 001-099 |
| 0033 | 22 | | GA | | 18-0 | 33-16-51 | SM00009 | | 9 | | TB0100Y | C009 | BJ | | 115-199 |
| 0034 | 22 | | GA | | 22-0 | 29-22-11 | D40570P | 3 | | | D41414P | 9 | | | 001-099 |
| 0034 | 22 | | GA | | 24-0 | 29-22-11 | D40570P | 3 | | | D41414P | 9 | | | 115-199 |
| 0035 | 22 | | GA | | 15-0 | 33-16-61 | SM00010 | | 9 | | D41174J | 9 | | | ALL |
| 0036 | 22 | | GA | | 7-0 | SPARE | D40570P | 6 | | | D41380P | 12 | | | 001-099 |
| 0036 | 22 | | GA | | 9-0 | SPARE | D40570P | 6 | | | D41380P | 12 | | | 115-199 |
| 0037 | 22 | | GA | | 17-0 | 33-16-51 | SM00004 | | 9 | | TB0100Y | C005 | BJ | | 001-099 |
| 0037 | 22 | | GA | | 18-0 | 33-16-51 | SM00004 | | 9 | | TB0100Y | C005 | BJ | | 115-199 |
| 0038 | 22 | | GA | | 17-0 | 33-16-61 | SM00011 | | 9 | | TB0100X | B001 | BJ | | 001-099 |
| 0038 | 22 | | GA | | 18-0 | 33-16-61 | SM00011 | | 9 | | TB0100X | B001 | BJ | | 115-199 |
| 0039 | 22 | | GA | | 18-0 | 33-16-61 | SM00011 | | 9 | | TB0058Z | 4 | BJ | | 001-099 |
| 0039 | 22 | | GA | | 19-0 | 33-16-61 | SM00011 | | 9 | | TB0058Z | 4 | BJ | | 115-199 |
| 0041 | 20 | | GA | | 8-0 | 33-13-31 | D02696 | 1 | | | TB0116X | C018 | BJ | | 001-099 |
| 0041 | 20 | | GA | | 7-0 | 33-13-31 | D02696 | 1 | | | TB0116X | C018 | BJ | | 115-199 |
| 0042 | 20 | | GA | | 7-0 | 33-13-31 | D02696 | 2 | | | TB0114Z | 12 | BJ | | ALL |
| 0043 | 20 | | GA | | 7-0 | 33-13-32 | D03508 | 1 | | | TB0115Z | 7 | BJ | | ALL |
| 0044 | 20 | | GA | | 7-0 | 33-13-32 | D03508 | 2 | | | TB0115Z | 8 | BJ | | ALL |
| 0047 | 22 | | GA | | 15-0 | 29-22-11 | TB0121Y | A023 | BJ | | D40806J | 8 | | | 001-099 |
| 0047 | 22 | | GA | | 32-0 | 29-22-11 | TB0121Y | A023 | BJ | | D40570P | 10 | | | 115-199 |
| 0048 | 22 | | GA | | 31-0 | 29-22-11 | TB0121X | D008 | BJ | | D40570P | 15 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 29

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0048 | 22 | | GA | | 32-0 | 29-22-11 | TB0121X | D008 | BJ | | D40570P | 15 | | | 115-199 |
| 0051 | 22 | | GA | | 31-0 | 29-22-11 | TB0121Y | C023 | BJ | | D40570P | 17 | | | 001-099 |
| 0051 | 22 | | GA | | 32-0 | 29-22-11 | TB0121Y | C023 | BJ | | D40570P | 17 | | | 115-199 |
| 0057 | 22 | | GA | | 15-0 | 33-16-51 | D41174J | 17 | | | SM00009 | | 9 | | ALL |
| 0058 | 22 | | GA | | 46-0 | 29-32-31 | D03548 | 5 | | | D41844P | 14 | | | 001-099 |
| 0058 | 22 | | GA | | 45-0 | 29-32-31 | D03548 | 5 | | | D41844P | 14 | | | 115-199 |
| 0059 | 22 | | GA | | 46-0 | 29-32-31 | D03548 | 6 | | | D41844P | 15 | | | 001-099 |
| 0059 | 22 | | GA | | 45-0 | 29-32-31 | D03548 | 6 | | | D41844P | 15 | | | 115-199 |
| 0061 | 22 | | GA | | 37-0 | 26-11-21 | TB0112A | C022 | 2 | | D40570P | 46 | | | 001-099 |
| 0061 | 22 | | GA | | 41-0 | 26-11-21 | D40806J | 14 | | | D40570P | 46 | | | 115-199 |
| 0062 | 22 | | GA | | 31-0 | 26-15-12 | D41414P | 1 | | | D40806J | 17 | | | 001-099 |
| 0062 | 22 | | GA | | 32-0 | 26-15-12 | D41414P | 1 | | | D40806J | 17 | | | 115-199 |
| 0063 | 22 | | GA | | 32-0 | 26-15-12 | D41414P | 2 | | | TB0115X | B004 | BJ | | 001-099 |
| 0063 | 22 | | GA | | 33-0 | 26-15-12 | D41414P | 2 | | | TB0115X | B004 | BJ | | 115-199 |
| 0064 | 24 | | GK | | 14-0 | 24-33-11 | D40296P | 34 | | | D03508 | 31 | | | ALL |
| 0065 | 24 | | GK | | 34-0 | 31-51-41 | D03706 | 14 | | | D40570P | 16 | | | ALL |
| 0066 | 24 | | GK | | 34-0 | 31-51-42 | D03706 | 10 | | | D40570P | 14 | | | ALL |
| 0069 | 24 | | GK | | 29-0 | 36-11-41 | TB0058X | A002 | BJ | | D03542 | 2 | | | 001-099 |
| 0069 | 24 | | GK | | 40-0 | 36-11-41 | D40570P | 11 | | | D03542 | 2 | | | 115-199 |
| 0070 | 24 | | GK | | 26-0 | 77-12-11 | D40806J | 18 | | | D41878J | 12 | | | 001-099 |
| 0070 | 24 | | GK | | 27-0 | 77-12-11 | D40806J | 18 | | | D41878J | 12 | | | 115-199 |
| 0071 | 22 | | GA | | 6-0 | 22-21-11 | D40806J | 5 | | | D03511 | 6 | | | 001-099 |
| 0071 | 22 | | GA | | 5-0 | 22-21-11 | D40806J | 5 | | | D03511 | 6 | | | 115-199 |
| 0072 | 24 | | GK | | 5-0 | 24-33-11 | D03508 | 29 | | | GD00600 | DC.. | 2 | | 001-099 |
| 0072 | 22 | | GA | | 4-0 | 24-33-11 | D03508 | 29 | | | GD00600 | DC.. | 2 | | 115-199 |
| 0073 | 22 | | GA | | 16-0 | 31-25-11 | D40296P | 24 | | | D41878J | 27 | | | 001-099 |
| 0073 | 22 | | GA | | 17-0 | 31-25-11 | D40296P | 24 | | | D41878J | 27 | | | 115-199 |
| 0074 | 20 | | GA | | 7-0 | 28-22-31 | TB0115X | A001 | BJ | | D03516 | 2 | | | ALL |
| 0075 | 20 | | GA | | 40-0 | 28-22-31 | D41850P | 1 | | | D03516 | 6 | | | 001-099 |
| 0075 | 20 | | GA | | 41-0 | 28-22-31 | D41850P | 1 | | | D03516 | 6 | | | 115-199 |
| 0077 | 22 | | GA | | 17-0 | 33-16-51 | SM00008 | | 9 | | TB0100Y | C010 | BJ | | 001-099 |
| 0077 | 22 | | GA | | 18-0 | 33-16-51 | SM00008 | | 9 | | TB0100Y | C010 | BJ | | 115-199 |
| 0081 | 22 | | GA | | 42-0 | 26-17-11 | D40806J | 27 | | | D41380P | 13 | | | 001-099 |
| 0081 | 22 | | GA | | 43-0 | 26-17-11 | D40806J | 27 | | | D41380P | 13 | | | 115-199 |
| 0082 | 22 | | GA | | 42-0 | 26-17-11 | D40806J | 35 | | | D41380P | 14 | | | 001-099 |
| 0082 | 22 | | GA | | 43-0 | 26-17-11 | D40806J | 35 | | | D41380P | 14 | | | 115-199 |
| 0084 | 20 | | GA | | 40-0 | 28-22-31 | D41850P | 2 | | | D03516 | 5 | | | 001-099 |
| 0084 | 20 | | GA | | 41-0 | 28-22-31 | D41850P | 2 | | | D03516 | 5 | | | 115-199 |
| 0085 | 24 | | GK | | 41-0 | 29-33-11 | D41850P | 17 | | | D03548 | 7 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 30

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0086 | 24 | | GK | | 30-0 | 28-22-31 | D41414P | | 6 | | D03516 | | 1 | | 001-099 |
| 0086 | 24 | | GK | | 31-0 | 28-22-31 | D41414P | | 6 | | D03516 | | 1 | | 115-199 |
| 0090 | 22 | | GA | | 42-0 | 26-16-11 | D40806J | | 26 | | D41380P | | 8 | | 001-099 |
| 0090 | 22 | | GA | | 43-0 | 26-16-11 | D40806J | | 26 | | D41380P | | 8 | | 115-199 |
| 0091 | 22 | | GA | | 30-0 | 26-11-11 | D40806J | | 28 | | TB0100X | A001 | BJ | | 115-199 |
| 0092 | 22 | | GA | | 39-0 | 26-15-11 | TB0112A | C020 | 2 | | D41380P | | 7 | | 001-099 |
| 0092 | 22 | | GA | | 43-0 | 26-15-11 | D40806J | | 15 | | D41380P | | 7 | | 115-199 |
| 0096 | 20 | | GA | | 7-0 | 26-21-11 | D40296P | | 9 | | D44102J | | 1 | | ALL |
| 0097 | 20 | | GA | | 7-0 | 26-21-11 | D40296P | | 10 | | D44104J | | 2 | | ALL |
| 0101 | 22 | | GA | | 46-0 | 22-21-11 | D03511 | | 5 | | D40600P | | 15 | | ALL |
| 0102 | 22 | | GA | | 46-0 | 22-21-11 | D03511 | | 7 | | D40600P | | 16 | | ALL |
| 0103 | 20 | | GA | | 5-0 | 22-21-11 | D03511 | | 12 | | GD00604 | DC.. | 2 | | 001-099 |
| 0103 | 20 | | GA | | 4-0 | 22-21-11 | D03511 | | 12 | | GD00604 | DC.. | 2 | | 115-199 |
| 0110 | 20 | | GA | | 8-0 | 33-42-21 | D03501 | | 12 | | TB0115X | B002 | BJ | | 001-099 |
| 0110 | 20 | | GA | | 7-0 | 33-42-21 | D03501 | | 12 | | TB0115X | B002 | BJ | | 115-199 |
| 0112 | 22 | | GA | | 16-0 | 31-25-11 | D40296P | | 22 | | D41174J | | 11 | | 001-099 |
| 0112 | 22 | | GA | | 17-0 | 31-25-11 | D40296P | | 22 | | D41174J | | 11 | | 115-199 |
| 0114 | 20 | | GA | | 31-0 | 33-42-21 | D03501 | | 13 | | D41414P | | 4 | | 001-099 |
| 0114 | 20 | | GA | | 32-0 | 33-42-21 | D03501 | | 13 | | D41414P | | 4 | | 115-199 |
| 0117 | 20 | | GA | | 8-0 | 33-13-31 | D03501 | | 2 | | TB0114Z | | 12 | BJ | ALL |
| 0118 | 20 | | GA | | 8-0 | 33-13-31 | D03501 | | 1 | | TB0114Z | | 11 | BJ | ALL |
| 0126 | 24 | | GK | | 23-0 | SPARE | D41844P | | 3 | | D40570P | | 8 | | 115-199 |
| 0127 | 24 | | GK | | 22-0 | 36-11-41 | D41844P | | 4 | | D40570P | | 13 | | 001-099 |
| 0127 | 24 | | GK | | 23-0 | 36-11-41 | D41844P | | 4 | | D40570P | | 13 | | 115-199 |
| 0130 | 24 | | GK | | 22-0 | 21-58-12 | D41844P | | 8 | | D40570P | | 27 | | 001-099 |
| 0130 | 24 | | GK | | 23-0 | 21-58-12 | D41844P | | 8 | | D40570P | | 27 | | 115-199 |
| 0131 | 24 | | GK | | 22-0 | 21-58-21 | D41844P | | 9 | | D40570P | | 28 | | 001-099 |
| 0131 | 24 | | GK | | 23-0 | 21-58-21 | D41844P | | 9 | | D40570P | | 28 | | 115-199 |
| 0143 | 20 | | GA | | 5-0 | 33-42-31 | D03501 | | 10 | | TB0113Y | C005 | BJ | | 001-099 |
| 0144 | 20 | | GA | | 31-0 | 33-42-31 | D03501 | | 11 | | D41414P | | 10 | | 001-099 |
| 0145 | 20 | | GA | | 27-0 | 26-22-21 | D41414P | | 15 | | TB0058Y | C005 | BJ | | 001-099 |
| 0147 | 16 | | GA | | 14-0 | 24-11-11 | D03504 | | 1 | | D40296P | | 21 | | ALL |
| 0148 | 16 | | GA | | 14-0 | 24-11-21 | D03504 | | 3 | | D40296P | | 23 | | ALL |
| 0150 | 22 | | GA | | 14-0 | 24-31-11 | D03508 | | 17 | | D40296P | | 7 | | ALL |
| 0151 | 24 | | GK | | 14-0 | 24-33-11 | D03508 | | 23 | | D40296P | | 1 | | 001-099 |
| 0151 | 22 | | GA | | 14-0 | 24-33-11 | D03508 | | 23 | | D40296P | | 1 | | 115-199 |
| 0152 | 24 | | GK | | 14-0 | 24-33-11 | D03508 | | 21 | | D40296P | | 2 | | 001-099 |
| 0152 | 22 | | GA | | 14-0 | 24-33-11 | D03508 | | 21 | | D40296P | | 2 | | 115-199 |
| 0153 | 24 | | GK | | 14-0 | 24-33-11 | D03508 | | 13 | | D40296P | | 3 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 31

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0153 | 22 | | GA | | 14-0 | 24-33-11 | D03508 | | 13 | | D40296P | | 3 | | 115-199 |
| 0154 | 18 | | GA | | 14-0 | 24-33-11 | D03508 | | 20 | 18 | D40296P | | 28 | 18 | ALL |
| 0155 | 24 | | GK | | 14-0 | 24-33-11 | D03508 | | 10 | | D40296P | | 4 | | 001-099 |
| 0155 | 22 | | GA | | 14-0 | 24-33-11 | D03508 | | 10 | | D40296P | | 4 | | 115-199 |
| 0156 | 24 | | GK | | 14-0 | 24-33-11 | D03508 | | 7 | | D40296P | | 6 | | 001-099 |
| 0156 | 22 | | GA | | 14-0 | 24-33-11 | D03508 | | 7 | | D40296P | | 6 | | 115-199 |
| 0157 | 24 | | GK | | 4-0 | 24-33-11 | SM00001 | | | 9 | D40296P | | 5 | | 001-099 |
| 0157 | 22 | | GA | | 4-0 | 24-33-11 | SM00001 | | | 9 | D40296P | | 5 | | 115-199 |
| 0158 | 24 | | GK | | 14-0 | 24-33-11 | D03508 | | 5 | | SM00001 | | | 9 | 001-099 |
| 0158 | 22 | | GA | | 14-0 | 24-33-11 | D03508 | | 5 | | SM00001 | | | 9 | 115-199 |
| 0159 | 24 | | GK | | 34-0 | 24-33-11 | D41844P | | 1 | | SM00001 | | | 9 | 001-099 |
| 0159 | 22 | | GA | | 33-0 | 24-33-11 | D41844P | | 1 | | SM00001 | | | 9 | 115-199 |
| 0160 | 24 | | GK | | 46-0 | 24-33-11 | D03508 | | 25 | | D41844P | | 2 | | 001-099 |
| 0160 | 22 | | GA | | 45-0 | 24-33-11 | D03508 | | 25 | | D41844P | | 2 | | 115-199 |
| 0161 | 20 | | GA | | 5-0 | 24-33-11 | D03508 | | 19 | | GD00600 | DC.. | 2 | | 001-099 |
| 0161 | 20 | | GA | | 4-0 | 24-33-11 | D03508 | | 19 | | GD00600 | DC.. | 2 | | 115-199 |
| 0162 | 24 | | GK | | 5-0 | 24-33-11 | D03508 | | 12 | | GD00600 | DC.. | 2 | | 001-099 |
| 0162 | 20 | | GA | | 4-0 | 24-33-11 | D03508 | | 12 | | GD00600 | DC.. | 2 | | 115-199 |
| 0163 | 18 | | GA | | 5-0 | 24-33-11 | D03508 | | 22 | 18 | GD00600 | AC.. | 2 | | 001-099 |
| 0163 | 18 | | GA | | 4-0 | 24-33-11 | D03508 | | 22 | 18 | GD00600 | AC.. | 2 | | 115-199 |
| 0164 | 24 | | GK | | 5-0 | 24-33-11 | D03508 | | 11 | | GD00600 | DC.. | 2 | | 001-099 |
| 0164 | 20 | | GA | | 4-0 | 24-33-11 | D03508 | | 11 | | GD00600 | DC.. | 2 | | 115-199 |
| 0165 | 24 | | GK | | 9-0 | 21-33-11 | D02696 | | 3 | | D40806J | | 19 | | 001-099 |
| 0165 | 24 | | GK | | 8-0 | 21-33-11 | D02696 | | 3 | | D40806J | | 19 | | 115-199 |
| 0166 | 24 | | GK | | 7-0 | 21-33-11 | D02696 | | 4 | | GD00604 | AC.. | 2 | | 001-099 |
| 0166 | 24 | | GK | | 5-0 | 21-33-11 | D02696 | | 4 | | GD00604 | AC.. | 2 | | 115-199 |
| 0167 | 20 | | GA | | 8-0 | 21-31-31 | D02346 | | 8 | | D40806J | | 3 | | 001-099 |
| 0167 | 20 | | GA | | 7-0 | 21-31-31 | D02346 | | 8 | | D40806J | | 3 | | 115-199 |
| 0168 | 20 | | GA | | 2-0 | 21-31-31 | D02346 | | 9 | | D02346 | | 10 | | 001-003, 005, 007-099 |
| 0168 | 20 | | GA | | 2-0 | 21-31-31 | D02346 | | 11 | | D02346 | | 10 | | 004, 006 |
| 0168 | 20 | | GA | | 1-0 | 21-31-31 | D02346 | | 9 | | D02346 | | 10 | | 115-199 |
| 0172 | 18 | | GA | | 16-0 | SPARE | D40296P | | 12 | 18 | D41174J | | 21 | 18 | 001-099 |
| 0172 | 18 | | GA | | 17-0 | SPARE | D40296P | | 12 | 18 | D41174J | | 21 | 18 | 115-199 |
| 0174 | 22 | | GA | | 9-0 | 33-16-52 | TB0116Y | C002 | | BJ | TB0115Z | | 10 | BJ | ALL |
| 0175 | 24 | | GK | | 45-0 | 36-11-41 | D41844P | | 5 | | D03542 | | 7 | | 001-099 |
| 0175 | 24 | | GK | | 44-0 | 36-11-41 | D41844P | | 5 | | D03542 | | 7 | | 115-199 |
| 0176 | 22 | | GA | | 8-0 | 31-51-41 | D03706 | | 15 | | GD00618 | DC.. | 2 | | 001-099 |
| 0176 | 22 | | GA | | 7-0 | 31-51-41 | D03706 | | 15 | | GD00618 | DC.. | 2 | | 115-199 |
| 0177 | 22 | | GA | | 8-0 | 31-51-42 | D03706 | | 11 | | GD00618 | DC.. | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 32

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0177 | 22 | | GA | | 7-0 | 31-51-42 | D03706 | | 11 | | GD00618 | DC.. | 2 | | 115-199 |
| 0180 | 24 | | GK | | 34-0 | 21-58-12 | D03706 | | 41 | | D40570P | | 49 | | ALL |
| 0181 | 24 | | GK | | 7-0 | 21-58-12 | D03706 | | 38 | | D40296P | | 39 | | ALL |
| 0182 | 20 | | GA | | 8-0 | 21-58-12 | D03706 | | 22 | | GD00618 | DC.. | 2 | | 001-099 |
| 0182 | 20 | | GA | | 7-0 | 21-58-12 | D03706 | | 22 | | GD00618 | DC.. | 2 | | 115-199 |
| 0185 | 24 | | GK | | 13-0 | 21-58-12 | D41844P | | 6 | | D41850P | | 9 | | ALL |
| 0186 | 24 | | GK | | 17-0 | 33-11-11 | D41010P | | 19 | | D41878J | | 1 | | ALL |
| 0187 | 24 | | GK | | 17-0 | 33-11-11 | D41010P | | 20 | | D41878J | | 2 | | ALL |
| 0188 | 22 | | GA | | 20-0 | 28-25-21 | D40296P | | 36 | | TB0058X | A012 | BJ | | 001-099 |
| 0188 | 22 | | GA | | 21-0 | 28-25-21 | D40296P | | 36 | | TB0058X | A012 | BJ | | 115-199 |
| 0189 | 22 | | GA | | 9-0 | 33-16-52 | TB0116Z | | 10 | BJ | TB0115Z | | 11 | BJ | ALL |
| 0190 | 24 | | GK | | 4-0 | 33-11-11 | D41010P | | 13 | | SM00002 | | 9 | | 001-099 |
| 0190 | 24 | | GK | | 2-0 | 33-11-11 | D41010P | | 13 | | SM00002 | | 9 | | 115-199 |
| 0191 | 24 | | GK | | 8-0 | 33-11-21 | TB0115X | D015 | BJ | | D03501 | | 4 | | 001-099 |
| 0191 | 24 | | GK | | 7-0 | 33-11-21 | TB0115X | D015 | BJ | | D03501 | | 4 | | 115-199 |
| 0192 | 24 | | GK | | 13-0 | 29-33-11 | D41844P | | 24 | | D41850P | | 4 | | 001-099 |
| 0192 | 24 | | GK | | 13-0 | 29-33-11 | D41844P | | 32 | | D41850P | | 4 | | 115-199 |
| 0193 | 24 | | GK | | 18-0 | 29-33-11 | D41850P | | 5 | | D40570P | | 7 | | 001-099 |
| 0193 | 24 | | GK | | 19-0 | 29-33-11 | D41850P | | 5 | | D40570P | | 7 | | 115-199 |
| 0194 | 24 | | GK | | 5-0 | 33-11-21 | D03501 | | 3 | | SM00019 | | 9 | | 001-099 |
| 0194 | 24 | | GK | | 5-0 | 33-11-21 | D03501 | | 3 | | SP01464 | | 9 | | 115-199 |
| 0195 | 22 | | GA | | 30-0 | 30-21-11 | D41380P | | 9 | | SM00025 | | 9 | | 001-099 |
| 0195 | 22 | | GA | | 31-0 | 30-21-11 | D41380P | | 9 | | SM00025 | | 9 | | 115-199 |
| 0196 | 20 | | GA | | 43-0 | 21-51-23 | D40806J | | 6 | | D41380P | | 10 | | 115-199 |
| 0197 | 20 | | GA | | 23-0 | 24-11-21 | D40570P | | 42 | | D40600P | | 23 | | 001-099 |
| 0197 | 20 | | GA | | 24-0 | 24-11-21 | D40570P | | 42 | | D40600P | | 23 | | 115-199 |
| 0198 | 24 | | GK | | 15-0 | 33-11-31 | D41008P | | 6 | | TB0115Y | C006 | BJ | | ALL |
| 0199 | 24 | | GK | | 11-0 | 33-11-31 | D41008P | | 22 | | SM00021 | | 9 | | 001-099 |
| 0199 | 24 | | GK | | 12-0 | 33-11-31 | D41008P | | 22 | | L00276 | =P | C | | 115-199 |
| 0200 | 22 | | GA | | 12-0 | 33-11-31 | GD00618 | AC.. | 2 | | L00276 | =G | C | | 115-199 |
| 0201 | 22 | | GA | | 17-0 | 33-11-31 | L00275 | =P | C | | D41008P | | 7 | | 115-199 |
| 0202 | 22 | | GA | | 8-0 | 33-11-31 | L00275 | =G | C | | GD00600 | AC.. | 2 | | 115-199 |
| 0204 | 24 | | GK | | 8-0 | 33-11-41 | D03501 | | 5 | | TB0115Y | C006 | BJ | | 001-099 |
| 0204 | 24 | | GK | | 7-0 | 33-11-41 | D03501 | | 5 | | TB0115Y | C006 | BJ | | 115-199 |
| 0205 | 24 | | GK | | 9-0 | 33-11-41 | D03501 | | 6 | | TB0116X | D012 | BJ | | 001-099 |
| 0205 | 24 | | GK | | 8-0 | 33-11-41 | D03501 | | 6 | | TB0116X | D012 | BJ | | 115-199 |
| 0210 | 22 | | GA | | 6-0 | 21-31-11 | D02346 | | 1 | | GD00604 | DC.. | 2 | | 001-099 |
| 0210 | 22 | | GA | | 5-0 | 21-31-11 | D02346 | | 1 | | GD00604 | DC.. | 2 | | 115-199 |
| 0212 | 22 | | GA | | 19-0 | 29-22-11 | D40570P | | 24 | | D41850P | | 31 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 33

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2078 | 286N2078 | | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0214 | 22 | | GA | | 7-0 | 33-16-51 | D40806J | | 12 | | | TB0115Y | C017 | BJ | | 001-099 |
| 0214 | 22 | | GA | | 7-0 | 33-16-51 | D40806J | | 12 | | | SP01934 | | 9 | | 115-199 |
| 0215 | 22 | | GA | | 14-0 | 33-16-51 | D40806J | | 13 | | | D41008P | | 3 | | ALL |
| 0216 | 20 | | GA | | 3-0 | 33-16-51 | GD01221 | DC.. | 2 | | | D41008P | | 21 | | ALL |
| 0217 | 20 | | GA | | 3-0 | 33-16-51 | GD01221 | DC.. | 2 | | | D41008P | | 12 | | ALL |
| 0218 | 22 | | GA | | 4-0 | 33-16-51 | SM00003 | | 9 | | | D41008P | | 20 | | ALL |
| 0219 | 20 | | GA | | 3-0 | 33-16-51 | GD01221 | DC.. | 2 | | | D41008P | | 10 | | ALL |
| 0220 | 20 | | GA | | 3-0 | 33-16-51 | GD01221 | DC.. | 2 | | | D41008P | | 14 | | ALL |
| 0221 | 22 | | GA | | 4-0 | 33-16-51 | SM00005 | | 9 | | | D41008P | | 16 | | ALL |
| 0222 | 22 | | GA | | 4-0 | 33-16-51 | SM00006 | | 9 | | | D41008P | | 9 | | ALL |
| 0223 | 22 | | GA | | 4-0 | 33-16-51 | SM00007 | | 9 | | | D41008P | | 13 | | ALL |
| 0224 | 22 | | GA | | 4-0 | 33-16-51 | SM00008 | | 9 | | | D41008P | | 4 | | ALL |
| 0225 | 22 | | GA | | 4-0 | 33-16-51 | SM00009 | | 9 | | | D41008P | | 11 | | ALL |
| 0226 | 22 | | GA | | 15-0 | 33-16-51 | D41878J | | 15 | | | SM00003 | | 9 | | ALL |
| 0227 | 22 | | GA | | 16-0 | 33-16-51 | D41878J | | 16 | | | D41008P | | 1 | | ALL |
| 0229 | 22 | | GA | | 15-0 | 33-16-51 | D41878J | | 11 | | | SM00007 | | 9 | | 115-199 |
| 0230 | 22 | | GA | | 16-0 | 33-16-51 | D41878J | | 18 | | | D41008P | | 2 | | ALL |
| 0231 | 22 | | GA | | 15-0 | 33-16-51 | D41878J | | 13 | | | SM00005 | | 9 | | ALL |
| 0232 | 22 | | GA | | 15-0 | 33-16-51 | D41878J | | 14 | | | SM00006 | | 9 | | ALL |
| 0235 | 22 | | GA | | 19-0 | 26-15-11 | D41380P | | 5 | | | D41850P | | 14 | | 001-099 |
| 0236 | 22 | | GA | | 19-0 | 26-15-11 | D41380P | | 6 | | | D41850P | | 13 | | 001-099 |
| 0238 | 24 | | GK | | 15-0 | 33-16-52 | TB0115X | C002 | BJ | | | D41008P | | 19 | | ALL |
| 0241 | 22 | | GA | | 14-0 | 33-16-61 | D40806J | | 23 | | | D41010P | | 22 | | ALL |
| 0242 | 22 | | GA | | 14-0 | 33-16-61 | D40806J | | 24 | | | D41010P | | 2 | | ALL |
| 0243 | 22 | | GA | | 14-0 | 33-16-61 | D40806J | | 22 | | | D41010P | | 11 | | ALL |
| 0244 | 20 | | GA | | 3-0 | 33-16-61 | GD01221 | DC.. | 2 | | | D41010P | | 6 | | ALL |
| 0245 | 22 | | GA | | 4-0 | 33-16-61 | SM00010 | | 9 | | | D41010P | | 4 | | ALL |
| 0246 | 22 | | GA | | 4-0 | 33-16-61 | SM00011 | | 9 | | | D41010P | | 3 | | ALL |
| 0247 | 22 | | GA | | 11-0 | 33-16-61 | TB0116X | A011 | BJ | | | D41010P | | 12 | | ALL |
| 0248 | 22 | | GA | | 15-0 | 33-16-61 | SM00011 | | 9 | | | D41878J | | 17 | | ALL |
| 0249 | 22 | | GA | | 11-0 | 33-16-62 | TB0116X | B011 | BJ | | | D41010P | | 5 | | ALL |
| 0250 | 22 | | GA | | 11-0 | 33-16-62 | TB0116Y | C005 | BJ | | | D41010P | | 1 | | ALL |
| 0251 | 22 | | GA | | 8-0 | 33-16-52 | D03548 | | 3 | | | TB0116Y | C002 | BJ | | ALL |
| 0252 | 22 | | GA | | 8-0 | 33-16-52 | D03548 | | 4 | | | TB0114Z | | 21 | BJ | 001-099 |
| 0252 | 22 | | GA | | 7-0 | 33-16-52 | D03548 | | 4 | | | TB0114Z | | 21 | BJ | 115-199 |
| 0253 | 22 | | GA | | 7-0 | 33-16-52 | D03516 | | 3 | | | TB0115Z | | 10 | BJ | ALL |
| 0254 | 22 | | GA | | 7-0 | 33-16-52 | D03516 | | 4 | | | TB0116Z | | 14 | BJ | ALL |
| 0255 | 22 | | GA | | 8-0 | 33-16-52 | D03508 | | 3 | | | TB0116Z | | 9 | BJ | ALL |
| 0256 | 22 | | GA | | 7-0 | 33-16-52 | D03508 | | 4 | | | TB0115Z | | 11 | BJ | ALL |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 34

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|--------|---------|------|-------------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | | |
| 0266 | 20 | GA | | | 3-0 | 33-11-11 | D41010P | 24 | | | | GD01221 | AC.. | 2 | | ALL |
| 0267 | 22 | GA | | | 7-0 | 31-51-11 | D40806J | 10 | | | | TB0115X | C001 | BJ | | ALL |
| 0268 | 22 | GA | | | 7-0 | 30-21-11 | D03528 | 7 | | | | D40806J | 30 | | | 001-099 |
| 0268 | 22 | GA | | | 6-0 | 30-21-11 | D03528 | 7 | | | | D40806J | 30 | | | 115-199 |
| 0270 | 22 | GA | | | 41-0 | 30-21-11 | D03528 | 8 | | | | D41850P | 10 | | | ALL |
| 0271 | 22 | GA | | | 41-0 | 30-21-11 | D03528 | 1 | | | | D41850P | 11 | | | ALL |
| 0272 | 20 | GA | | | 41-0 | 74-31-11 | D03528 | 9 | | | | D41850P | 27 | | | ALL |
| 0273 | 20 | GA | | | 41-0 | 74-31-11 | D03528 | 10 | | | | D41850P | 21 | | | ALL |
| 0275 | 22 | GA | | | 15-0 | 24-34-11 | D40296P | 8 | | | | TB0115X | C004 | BJ | | ALL |
| 0277 | 22 | GA | | | 8-0 | 33-16-62 | D03528 | 3 | | | | TB0116Y | A001 | BJ | | ALL |
| 0278 | 22 | GA | | | 8-0 | 33-16-52 | D03528 | 4 | | | | TB0116Z | 10 | BJ | | ALL |
| 0279 | 22 | GA | | | 6-0 | 33-16-52 | TB0116Z | 3 | BJ | | | TB0114Z | 21 | BJ | | ALL |
| 0281 | 24 | GK | | | 28-0 | 28-22-31 | D41414P | 7 | | | | D41844P | 10 | | | ALL |
| 0282 | 20 | GA | | | 28-0 | 28-22-31 | D41414P | 8 | | | | D41844P | 11 | | | ALL |
| 0283 | 20 | GA | | | 21-0 | 26-22-21 | D40296P | 37 | | | | D41414P | 52 | | | 001-099 |
| 0283 | 22 | GA | | | 21-0 | 26-15-11 | D41850P | 13 | | | | D41380P | 5 | | | 115-199 |
| 0284 | 20 | GA | | | 22-0 | 26-22-21 | TB0121Y | C024 | BJ | | | D41414P | 51 | | | 001-099 |
| 0284 | 22 | GA | | | 21-0 | 26-15-11 | D41850P | 14 | | | | D41380P | 6 | | | 115-199 |
| 0285 | 20 | GA | | | 8-0 | 26-21-11 | D03734 | 3 | | | | D40296P | 14 | | | 001-099 |
| 0285 | 20 | GA | | | 7-0 | 26-21-11 | D03734 | 3 | | | | D40296P | 14 | | | 115-199 |
| 0286 | 20 | GA | | | 8-0 | 26-21-11 | D03734 | 4 | | | | D40296P | 15 | | | 001-099 |
| 0286 | 20 | GA | | | 7-0 | 26-21-11 | D03734 | 4 | | | | D40296P | 15 | | | 115-199 |
| 0287 | 20 | GA | | | 5-0 | 26-21-11 | D03734 | 9 | | | | D44102J | 4 | | | 001-099 |
| 0287 | 20 | GA | | | 4-0 | 26-21-11 | D03734 | 9 | | | | D44102J | 4 | | | 115-199 |
| 0288 | 20 | GA | | | 25-0 | 26-21-11 | D03734 | 8 | | | | D41414P | 16 | | | ALL |
| 0289 | 20 | GA | | | 8-0 | 26-21-11 | D03734 | 5 | | | | GD00618 | DC.. | 2 | | 001-099 |
| 0289 | 20 | GA | | | 7-0 | 26-21-11 | D03734 | 5 | | | | GD00618 | DC.. | 2 | | 115-199 |
| 0290 | 20 | GA | | | 8-0 | 26-21-11 | D03734 | 2 | | | | GD00618 | ST.. | 2 | | 001-099 |
| 0290 | 20 | GA | | | 7-0 | 26-21-11 | D03734 | 2 | | | | GD00618 | ST.. | 2 | | 115-199 |
| 0291 | 20 | GA | | | 8-0 | 26-23-11 | D40296P | 16 | | | | SM00018 | | 9 | | 001-099 |
| 0291 | 20 | GA | | | 6-10 | 26-23-11 | D40296P | 16 | | | | SM00018 | | 9 | | 115-199 |
| 0292 | 20 | GA | | | 1-0 | 26-23-11 | D03734 | 6 | | | | SM00018 | | 9 | | 001-099 |
| 0292 | 20 | GA | | | 7-0 | 26-23-11 | D03734 | 6 | | | | SM00018 | | 9 | | 115-199 |
| 0293 | 20 | GA | | | 5-0 | 26-23-11 | D03734 | 10 | | | | D44102J | 2 | | | 001-099 |
| 0293 | 20 | GA | | | 4-0 | 26-23-11 | D03734 | 10 | | | | D44102J | 2 | | | 115-199 |
| 0294 | 20 | GA | | | 5-0 | 26-23-11 | D03734 | 11 | | | | D44104J | 3 | | | 001-099 |
| 0294 | 20 | GA | | | 4-0 | 26-23-11 | D03734 | 11 | | | | D44104J | 3 | | | 115-199 |
| 0295 | 22 | GA | | | 23-0 | 26-15-11 | D41850P | 15 | | | | D41414P | 11 | | | 001-099 |
| 0295 | 22 | GA | | | 24-0 | 26-15-11 | D41850P | 15 | | | | D41414P | 11 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 35

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0296 | 22 | GA | | 23-0 | 26-15-11 | D41850P | | 16 | | | D41414P | 12 | | | 001-099 |
| 0296 | 22 | GA | | 24-0 | 26-15-11 | D41850P | | 16 | | | D41414P | 12 | | | 115-199 |
| 0297 | 22 | GA | | 11-0 | 33-16-52 | SM00007 | | | 9 | | TB0116Z | 3 | BJ | | ALL |
| 0298 | 22 | GA | | 11-0 | 33-16-52 | SM00006 | | | 9 | | TB0116Z | 10 | BJ | | ALL |
| 0299 | 22 | GA | | 11-0 | 33-16-52 | SM00005 | | | 9 | | TB0116Z | 9 | BJ | | ALL |
| 0300 | 22 | GA | | 11-0 | 33-16-52 | SM00009 | | | 9 | | TB0116Z | 14 | BJ | | ALL |
| 0301 | 22 | GA | | 11-0 | 33-16-52 | SM00008 | | | 9 | | TB0116Z | 13 | BJ | | ALL |
| 0302 | 22 | GA | | 11-0 | 33-16-53 | SM00005 | | | 9 | | TB0116Z | 9 | BJ | | 001-003, 115-199 |
| 0303 | 22 | GA | | 4-0 | 33-16-63 | SM00010 | | | 9 | | TB0121X | B006 | BJ | | 001-003, 115-199 |
| 0304 | 22 | GA | | 4-0 | 33-16-51 | SM00004 | | | 9 | | D41008P | 17 | | | ALL |
| 0305 | 22 | GA | | 15-0 | 33-16-52 | SM00004 | | | 9 | | TB0115Z | 10 | BJ | | ALL |
| 0306 | 22 | GA | | 15-0 | 33-16-62 | SM00011 | | | 9 | | TB0115X | A004 | BJ | | ALL |
| 0307 | 22 | GA | | 12-0 | 33-16-62 | SM00010 | | | | | TB0114Z | 22 | BJ | | ALL |
| 0308 | 22 | GA | | 11-0 | 33-16-52 | TB0116X | | B016 | BJ | | D41008P | 15 | | | ALL |
| 0309 | 22 | GA | | 11-0 | 33-16-52 | TB0116X | | A016 | BJ | | D41008P | 23 | | | ALL |
| 0310 | 24 | GK | | 36-0 | 21-25-11 | D40570P | | | 29 | | TB0058X | A011 | BJ | | 001-099 |
| 0310 | 24 | GK | | 38-0 | 21-25-11 | D40570P | | | 29 | | TB0058X | A011 | BJ | | 115-199 |
| 0311 | 20 | GA | | 7-0 | 33-13-31 | D03511 | | | 1 | | TB0114Z | 8 | BJ | | ALL |
| 0312 | 20 | GA | | 7-0 | 33-13-31 | D03511 | | | 2 | | TB0114Z | 10 | BJ | | ALL |
| 0313 | 22 | GA | | 7-0 | 33-16-52 | D03511 | | | 4 | | TB0114Z | 21 | BJ | | ALL |
| 0314 | 22 | GA | | 7-0 | 33-16-52 | D03511 | | | 3 | | TB0115Z | 10 | BJ | | 001-099 |
| 0314 | 22 | GA | | 6-0 | 33-16-52 | D03511 | | | 3 | | TB0115Z | 10 | BJ | | 115-199 |
| 0315 | 22 | GA | | 42-0 | 77-12-41 | D40806J | | | 1 | | D41380P | 4 | | | 001-099 |
| 0315 | 22 | GA | | 43-0 | 77-12-41 | D40806J | | | 1 | | D41380P | 4 | | | 115-199 |
| 0316 | 22 | GA | | 11-0 | 24-51-72 | D40296P | | | 29 | | TB0116X | A017 | BJ | | ALL |
| 0320 | 20 | GA | | 18-0 | 29-22-11 | D41850P | | | 18 | | D40570P | 18 | | | 001-099 |
| 0320 | 20 | GA | | 19-0 | 29-22-11 | D41850P | | | 18 | | D40570P | 18 | | | 115-199 |
| 0321 | 20 | GA | | 18-0 | 29-22-11 | D41850P | | | 19 | | D40570P | 19 | | | 001-099 |
| 0321 | 20 | GA | | 19-0 | 29-22-11 | D41850P | | | 19 | | D40570P | 19 | | | 115-199 |
| 0322 | 20 | GA | | 18-0 | 29-22-11 | D41850P | | | 20 | | D40570P | 20 | | | 001-099 |
| 0322 | 20 | GA | | 19-0 | 29-22-11 | D41850P | | | 20 | | D40570P | 20 | | | 115-199 |
| 0323 | 22 | GA | | 22-0 | 26-15-12 | D41414P | | | 14 | | D40570P | 21 | | | 001-099 |
| 0323 | 22 | GA | | 23-0 | 26-15-12 | D41414P | | | 14 | | D40570P | 21 | | | 115-199 |
| 0324 | 22 | GA | | 18-0 | 77-12-41 | D41850P | | | 22 | | D40570P | 22 | | | 001-099 |
| 0324 | 22 | GA | | 19-0 | 77-12-41 | D41850P | | | 22 | | D40570P | 22 | | | 115-199 |
| 0325 | 22 | GA | | 41-0 | 32-42-11 | D41850P | | | 23 | | D40806J | 29 | | | 001-099 |
| 0325 | 22 | GA | | 42-0 | 32-42-11 | D41850P | | | 23 | | D40806J | 29 | | | 115-199 |
| 0326 | 22 | GA | | 41-0 | 32-42-11 | D41850P | | | 24 | | D40806J | 31 | | | 001-099 |
| 0326 | 22 | GA | | 42-0 | 32-42-11 | D41850P | | | 24 | | D40806J | 31 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 36

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0327 | 20 | GA | | | 19-0 | SPARE | D41850P | | 25 | | D40570P | | 25 | | 115-199 |
| 0328 | 22 | GA | | | 23-0 | 26-15-12 | D41850P | | 26 | | D41414P | | 13 | | 001-099 |
| 0328 | 22 | GA | | | 24-0 | 26-15-12 | D41850P | | 26 | | D41414P | | 13 | | 115-199 |
| 0330 | 22 | GA | | | 23-0 | 26-15-12 | D41850P | | 28 | | D41414P | | 17 | | 001-099 |
| 0330 | 22 | GA | | | 24-0 | 26-15-12 | D41850P | | 28 | | D41414P | | 17 | | 115-199 |
| 0331 | 22 | GA | | | 23-0 | 26-15-12 | D41850P | | 29 | | D41414P | | 18 | | 001-099 |
| 0331 | 22 | GA | | | 24-0 | 26-15-12 | D41850P | | 29 | | D41414P | | 18 | | 115-199 |
| 0332 | 22 | GA | | | 23-0 | 26-15-12 | D41850P | | 30 | | D41414P | | 19 | | 001-099 |
| 0332 | 22 | GA | | | 24-0 | 26-15-12 | D41850P | | 30 | | D41414P | | 19 | | 115-199 |
| 0335 | 22 | GA | | | 23-0 | 26-15-12 | D41850P | | 33 | | D41414P | | 22 | | 001-099 |
| 0335 | 22 | GA | | | 24-0 | 26-15-12 | D41850P | | 33 | | D41414P | | 22 | | 115-199 |
| 0336 | 20 | GA | | | 23-0 | SPARE | D41850P | | 34 | | D41414P | | 23 | | 001-099 |
| 0336 | 20 | GA | | | 24-0 | 29-22-11 | D41850P | | 34 | | D41414P | | 23 | | 115-199 |
| 0337 | 20 | GA | | | 23-0 | SPARE | D41850P | | 35 | | D41414P | | 24 | | 001-099 |
| 0337 | 20 | GA | | | 24-0 | 29-22-11 | D41850P | | 35 | | D41414P | | 24 | | 115-199 |
| 0338 | 24 | GK | | | 13-0 | 21-58-12 | D41844P | | 7 | | D41850P | | 36 | | ALL |
| 0339 | 22 | GA | | | 14-0 | 32-42-11 | D41850P | | 37 | | D40600P | | 7 | | 001-099 |
| 0339 | 20 | GA | | | 13-0 | SPARE | D41850P | | 37 | | D41844P | | 17 | | 115-199 |
| 0340 | 22 | GA | | | 14-0 | 32-42-11 | D41850P | | 38 | | D40600P | | 8 | | 001-099 |
| 0340 | 20 | GA | | | 13-0 | SPARE | D41850P | | 38 | | D41844P | | 18 | | 115-199 |
| 0341 | 22 | GA | | | 14-0 | 32-42-11 | D41850P | | 39 | | D40600P | | 9 | | 001-099 |
| 0341 | 20 | GA | | | 13-0 | SPARE | D41850P | | 39 | | D41844P | | 19 | | 115-199 |
| 0342 | 22 | GA | | | 14-0 | 32-42-11 | D41850P | | 40 | | D40600P | | 10 | | 001-099 |
| 0342 | 20 | GA | | | 13-0 | SPARE | D41850P | | 40 | | D41844P | | 20 | | 115-199 |
| 0343 | 20 | GA | | | 14-0 | 21-25-11 | D41850P | | 41 | | D40600P | | 2 | | ALL |
| 0344 | 22 | GA | | | 14-0 | 32-42-11 | D41850P | | 42 | | D40600P | | 11 | | 001-099 |
| 0344 | 20 | GA | | | 14-0 | SPARE | D41850P | | 42 | | D40600P | | 3 | | 115-199 |
| 0345 | 22 | GA | | | 14-0 | SPARE | D41850P | | 43 | | D40600P | | 12 | | 001-099 |
| 0345 | 20 | GA | | | 14-0 | SPARE | D41850P | | 43 | | D40600P | | 4 | | 115-199 |
| 0346 | 22 | GA | | | 41-0 | SPARE | D41850P | | 44 | | D03511 | | 11 | | 115-199 |
| 0348 | 24 | GK | | | 31-0 | 24-34-11 | D41850P | | 46 | | D40296P | | 35 | | 001-099 |
| 0348 | 24 | GK | | | 32-0 | 24-34-11 | D41850P | | 46 | | D40296P | | 35 | | 115-199 |
| 0349 | 20 | GA | | | 41-0 | 30-21-11 | D41850P | | 47 | | D03528 | | 2 | | ALL |
| 0350 | 20 | GA | | | 29-0 | 30-21-11 | D41850P | | 48 | | SM00025 | | 9 | | 001-099 |
| 0350 | 20 | GA | | | 30-0 | 30-21-11 | D41850P | | 48 | | SM00025 | | 9 | | 115-199 |
| 0352 | 22 | GA | | | 14-0 | 32-44-11 | D41850P | | 50 | | D40600P | | 13 | | 001-099 |
| 0352 | 20 | GA | | | 42-0 | SPARE | D41850P | | 50 | | D03501 | CAP | Y | | 115-199 |
| 0353 | 20 | GA | | | 41-0 | SPARE | D41850P | | 51 | | D03528 | CAP | Y | | 115-199 |
| 0354 | 20 | GA | | | 41-0 | SPARE | D41850P | | 52 | | D03528 | CAP | Y | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 37

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0355 | 24 | | GK | | 35-0 | 21-58-12 | D41850P | | 53 | | D03706 | 21 | | | ALL |
| 0356 | 20 | | GA | | 35-0 | SPARE | D41850P | | 54 | | D03734 | CAP | Y | | 001-099 |
| 0356 | 20 | | GA | | 34-0 | SPARE | D41850P | | 54 | | D03734 | CAP | Y | | 115-199 |
| 0357 | 20 | | GA | | 32-0 | SPARE | D41850P | | 55 | | D40296P | 31 | | | 115-199 |
| 0358 | 20 | | GA | | 32-0 | SPARE | D41414P | | 25 | | D03501 | CAP | Y | | 115-199 |
| 0359 | 20 | | GA | | 32-0 | SPARE | D41414P | | 26 | | D03501 | CAP | Y | | 115-199 |
| 0360 | 20 | | GA | | 32-0 | SPARE | D41414P | | 27 | | D03528 | CAP | Y | | 115-199 |
| 0361 | 20 | | GA | | 32-0 | SPARE | D41414P | | 28 | | D03528 | CAP | Y | | 115-199 |
| 0362 | 20 | | GA | | 32-0 | SPARE | D41414P | | 29 | | D03528 | CAP | Y | | 115-199 |
| 0363 | 20 | | GA | | 32-0 | SPARE | D41414P | | 30 | | D03528 | CAP | Y | | 115-199 |
| 0364 | 20 | | GA | | 32-0 | SPARE | D41414P | | 31 | | D03528 | CAP | Y | | 115-199 |
| 0365 | 20 | | GA | | 31-0 | SPARE | D41414P | | 32 | | D02696 | CAP | Y | | 115-199 |
| 0366 | 20 | | GA | | 31-0 | SPARE | D41414P | | 33 | | D02696 | CAP | Y | | 115-199 |
| 0367 | 20 | | GA | | 31-0 | SPARE | D41414P | | 34 | | D02696 | CAP | Y | | 115-199 |
| 0368 | 20 | | GA | | 31-0 | SPARE | D41414P | | 35 | | D02696 | CAP | Y | | 115-199 |
| 0369 | 20 | | GA | | 31-0 | SPARE | D41414P | | 36 | | D02696 | CAP | Y | | 115-199 |
| 0370 | 20 | | GA | | 25-0 | SPARE | D41414P | | 37 | | D03734 | CAP | Y | | 115-199 |
| 0371 | 20 | | GA | | 25-0 | SPARE | D41414P | | 38 | | D03734 | CAP | Y | | ALL |
| 0372 | 20 | | GA | | 25-0 | SPARE | D41414P | | 39 | | D03734 | CAP | Y | | ALL |
| 0373 | 20 | | GA | | 21-0 | SPARE | D41414P | | 40 | | D40296P | 13 | | | 001-099 |
| 0373 | 20 | | GA | | 22-0 | SPARE | D41414P | | 40 | | D40296P | 13 | | | 115-199 |
| 0374 | 20 | | GA | | 21-0 | SPARE | D41414P | | 41 | | D40296P | 17 | | | 001-099 |
| 0374 | 20 | | GA | | 22-0 | SPARE | D41414P | | 41 | | D40296P | 17 | | | 115-199 |
| 0375 | 20 | | GA | | 22-0 | SPARE | D41414P | | 42 | | D40296P | 18 | | | 115-199 |
| 0376 | 20 | | GA | | 22-0 | SPARE | D41414P | | 43 | | D40296P | 19 | | | 115-199 |
| 0377 | 20 | | GA | | 24-0 | SPARE | D41414P | | 44 | | D41380P | 1 | | | 001-099 |
| 0377 | 20 | | GA | | 26-0 | SPARE | D41414P | | 44 | | D41380P | 1 | | | 115-199 |
| 0378 | 20 | | GA | | 24-0 | SPARE | D41414P | | 45 | | D41380P | 2 | | | 001-099 |
| 0378 | 20 | | GA | | 26-0 | SPARE | D41414P | | 45 | | D41380P | 2 | | | 115-199 |
| 0379 | 20 | | GA | | 26-0 | SPARE | D41414P | | 46 | | D41380P | 3 | | | 115-199 |
| 0380 | 20 | | GA | | 23-0 | SPARE | D41414P | | 47 | | D41174J | 2 | | | 001-099 |
| 0380 | 20 | | GA | | 24-0 | SPARE | D41414P | | 47 | | D41174J | 2 | | | 115-199 |
| 0381 | 20 | | GA | | 23-0 | SPARE | D41414P | | 48 | | D41174J | 3 | | | 001-099 |
| 0381 | 20 | | GA | | 24-0 | SPARE | D41414P | | 48 | | D41174J | 3 | | | 115-199 |
| 0382 | 20 | | GA | | 23-0 | SPARE | D41414P | | 49 | | D41878J | 8 | | | 001-008 |
| 0382 | 20 | | GA | | 24-0 | SPARE | D41414P | | 49 | | D41878J | 8 | | | 115-199 |
| 0383 | 24 | | GK | | 5-0 | 21-51-22 | D40806J | | 36 | | TB0113X | B016 | BJ | | ALL |
| 0384 | 24 | | GK | | 7-0 | 21-51-12 | D40806J | | 37 | | TB0115X | B016 | BJ | | ALL |
| 0387 | 20 | | GA | | 40-0 | SPARE | D40570P | | 30 | | D03528 | CAP | Y | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 38

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0387 | 20 | | GA | | 41-0 | SPARE | D40570P | | 30 | | D03528 | | CAP | Y | 115-199 |
| 0388 | 20 | | GA | | 40-0 | SPARE | D40570P | | 31 | | D03528 | | CAP | Y | 001-099 |
| 0388 | 20 | | GA | | 41-0 | SPARE | D40570P | | 31 | | D03528 | | CAP | Y | 115-199 |
| 0389 | 20 | | GA | | 40-0 | SPARE | D40570P | | 32 | | D02696 | | CAP | Y | 115-199 |
| 0390 | 20 | | GA | | 40-0 | SPARE | D40570P | | 33 | | D02696 | | CAP | Y | 115-199 |
| 0391 | 20 | | GA | | 40-0 | SPARE | D40570P | | 34 | | D02696 | | CAP | Y | 115-199 |
| 0392 | 20 | | GA | | 34-0 | SPARE | D40570P | | 35 | | D03734 | | CAP | Y | ALL |
| 0393 | 20 | | GA | | 34-0 | SPARE | D40570P | | 36 | | D03734 | | CAP | Y | ALL |
| 0394 | 20 | | GA | | 34-0 | SPARE | D40570P | | 37 | | D03734 | | CAP | Y | 115-199 |
| 0395 | 20 | | GA | | 30-0 | SPARE | D40570P | | 38 | | D40296P | 20 | | | 001-099 |
| 0395 | 20 | | GA | | 31-0 | SPARE | D40570P | | 38 | | D40296P | 20 | | | 115-199 |
| 0397 | 20 | | GA | | 30-0 | SPARE | D40570P | | 40 | | D40296P | 25 | | | 001-099 |
| 0397 | 20 | | GA | | 31-0 | SPARE | D40570P | | 40 | | D40296P | 25 | | | 115-199 |
| 0402 | 20 | | GA | | 46-0 | SPARE | D41844P | | 21 | | D03548 | | CAP | Y | 001-099 |
| 0402 | 20 | | GA | | 45-0 | SPARE | D41844P | | 21 | | D03548 | | CAP | Y | 115-199 |
| 0403 | 20 | | GA | | 46-0 | SPARE | D41844P | | 22 | | D03548 | | CAP | Y | 001-099 |
| 0403 | 20 | | GA | | 45-0 | SPARE | D41844P | | 22 | | D03548 | | CAP | Y | 115-199 |
| 0404 | 20 | | GA | | 45-0 | SPARE | D41844P | | 23 | | D03504 | | CAP | Y | 115-199 |
| 0405 | 20 | | GA | | 45-0 | SPARE | D41844P | | 24 | | D03504 | | CAP | Y | 115-199 |
| 0406 | 20 | | GA | | 45-0 | SPARE | D41844P | | 25 | | D03504 | | CAP | Y | 115-199 |
| 0407 | 20 | | GA | | 44-0 | SPARE | D41844P | | 26 | | D03516 | | CAP | Y | 115-199 |
| 0408 | 20 | | GA | | 44-0 | SPARE | D41844P | | 27 | | D03516 | | CAP | Y | 115-199 |
| 0409 | 20 | | GA | | 44-0 | SPARE | D41844P | | 28 | | D03516 | | CAP | Y | 115-199 |
| 0410 | 20 | | GA | | 44-0 | SPARE | D41844P | | 29 | | D02346 | | CAP | Y | 115-199 |
| 0411 | 20 | | GA | | 44-0 | SPARE | D41844P | | 30 | | D02346 | | CAP | Y | 115-199 |
| 0412 | 20 | | GA | | 44-0 | SPARE | D41844P | | 31 | | D02346 | | CAP | Y | 115-199 |
| 0416 | 20 | | GA | | 35-0 | SPARE | D41844P | | 35 | | D40296P | 26 | | | 115-199 |
| 0417 | 20 | | GA | | 35-0 | SPARE | D41844P | | 36 | | D40296P | 27 | | | 115-199 |
| 0418 | 20 | | GA | | 46-0 | 24-33-12 | D03508 | | 37 | | D41844P | 17 | | | 001-099 |
| 0419 | 20 | | GA | | 46-0 | 24-33-12 | D03508 | | 38 | | D41844P | 18 | | | 001-099 |
| 0420 | 20 | | GA | | 38-0 | SPARE | D41844P | | 23 | | D41878J | 20 | | | 001-099 |
| 0420 | 20 | | GA | | 38-0 | SPARE | D41844P | | 39 | | D41878J | 20 | | | 115-199 |
| 0421 | 24 | | GK | | 7-0 | 24-41-11 | D03508 | | 14 | | TB0115X | A002 | BJ | | 001-099 |
| 0421 | 20 | | GA | | 7-0 | 24-41-11 | D03508 | | 14 | | TB0115X | A002 | BJ | | 115-199 |
| 0422 | 22 | | GA | | 15-0 | 24-34-11 | D40296P | | 30 | | TB0115X | D004 | BJ | | ALL |
| 0423 | 20 | | GA | | 8-0 | 21-31-11 | D40806J | | 20 | | TB0112X | B004 | BJ | | ALL |
| 0424 | 24 | | GK | | 8-0 | 36-11-31 | D40806J | | 25 | | D03586 | 3 | | | ALL |
| 0425 | 24 | | GK | | 7-0 | 24-51-31 | D40806J | | 45 | | TB0111A | A008 | 2 | | 001-099 |
| 0426 | 24 | | GK | | 8-0 | 26-11-11 | D40806J | | 28 | | TB0112A | A024 | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 39

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2078 | 286N2078 | | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | |
| 0427 | 24 | | GK | | 3-0 | 26-11-11 | | TB0112A | C023 | 2 | | TB0112A | C024 | 2 | | 001-099 |
| 0428 | 24 | | GK | | 8-0 | 26-11-21 | | D40806J | | 14 | | TB0112A | A022 | 2 | | 001-099 |
| 0429 | 24 | | GK | | 8-0 | 26-15-11 | | D40806J | | 15 | | TB0112A | A020 | 2 | | 001-099 |
| 0430 | 22 | | GA | | 35-0 | 24-25-11 | | D03706 | | 2 | | D41850P | | 32 | | 001-002, 115-199 |
| 0430 | 22 | | GA | | 35-0 | 24-25-11 | | D03706 | | 1 | | D41850P | | 52 | | 003-099 |
| 0431 | 20 | | GA | | 8-0 | 24-25-11 | | D03706 | | 3 | | GD00618 | DC.. | 2 | | 001-002 |
| 0431 | 22 | | GA | | 35-0 | 24-25-11 | | D03706 | | 3 | | D41850P | | 25 | | 003-099 |
| 0431 | 22 | | GA | | 7-0 | 24-25-11 | | D03706 | | 3 | | GD00618 | DC.. | 2 | | 115-199 |
| 0432 | 24 | | GK | | 14-0 | 30-32-11 | | D40806J | | 38 | | SM00017 | | 9 | | ALL |
| 0433 | 24 | | GK | | 19-0 | 30-32-11 | | D41414P | | 53 | | SM00017 | | 9 | | 001-099 |
| 0433 | 24 | | GK | | 20-0 | 30-32-11 | | SM00017 | | | 9 | D41414P | | 53 | | 115-199 |
| 0434 | 22 | | GA | | 30-0 | 34-57-21 | | D40806J | | 39 | | TB0059X | D009 | BJ | | 001-099 |
| 0434 | 22 | | GA | | 32-0 | 34-57-21 | | D40806J | | 39 | | TB0059X | D009 | BJ | | 115-199 |
| 0435 | 22 | | GA | | 30-0 | 78-34-11 | | D40806J | | 40 | | TB0059Y | A006 | BJ | | 001-099 |
| 0435 | 22 | | GA | | 32-0 | 78-34-11 | | D40806J | | 40 | | TB0059Y | A006 | BJ | | 115-199 |
| 0436 | 24 | | GK | | 7-0 | 24-31-11 | | D03706 | | 5 | | D40296P | | 38 | | 001-002, 115-199 |
| 0436 | 24 | | GK | | 7-0 | 24-25-11 | | D03706 | | 5 | | D40296P | | 38 | | 003-099 |
| 0437 | 22 | | GA | | 8-0 | 24-31-11 | | D03706 | | 6 | | GD00619 | DC.. | 2 | | 001-002 |
| 0437 | 22 | | GA | | 8-0 | 24-25-11 | | D03706 | | 6 | | GD00619 | DC.. | 2 | | 003-099 |
| 0437 | 22 | | GA | | 7-0 | 24-31-11 | | D03706 | | 6 | | GD00619 | DC.. | 2 | | 115-199 |
| 0452 | 22 | | GA | | 14-0 | 30-11-11 | | D40806J | | 34 | | SM00016 | | 9 | | ALL |
| 0453 | 22 | | GA | | 8-0 | 30-11-11 | | D03706 | | 28 | | SM00016 | | 9 | | 001-099 |
| 0453 | 22 | | GA | | 7-0 | 30-11-11 | | SM00016 | | | 9 | D03706 | | 28 | | 115-199 |
| 0454 | 22 | | GA | | 14-0 | 30-11-11 | | D03550 | | 2 | | SM00016 | | 9 | | 001-099 |
| 0454 | 22 | | GA | | 14-0 | 30-11-11 | | SM00016 | | | 9 | D03550 | | 2 | | 115-199 |
| 0455 | 22 | | GA | | 40-0 | 30-11-11 | | D03550 | | 1 | | D40570P | | 43 | | 001-099 |
| 0455 | 22 | | GA | | 41-0 | 30-11-11 | | D03550 | | 1 | | D40570P | | 43 | | 115-199 |
| 0456 | 22 | | GA | | 46-0 | 30-11-11 | | D03550 | | 11 | | D41844P | | 20 | | 001-099 |
| 0456 | 22 | | GA | | 5-0 | 30-11-11 | | D03550 | | 11 | | TB0113Y | C004 | BJ | | 115-199 |
| 0457 | 22 | | GA | | 29-0 | 30-11-11 | | D03550 | | 9 | | TB0100X | A002 | BJ | | 001-099 |
| 0457 | 22 | | GA | | 30-0 | 30-11-11 | | D03550 | | 9 | | TB0100X | A002 | BJ | | 115-199 |
| 0458 | 22 | | GA | | 29-0 | 30-11-11 | | D03550 | | 8 | | TB0100X | B002 | BJ | | 001-099 |
| 0458 | 22 | | GA | | 30-0 | 30-11-11 | | D03550 | | 8 | | TB0100X | B002 | BJ | | 115-199 |
| 0459 | 22 | | GA | | 46-0 | 30-11-11 | | D03550 | | 5 | | D41844P | | 19 | | 001-099 |
| 0459 | 22 | | GA | | 5-0 | 30-11-11 | | D03550 | | 5 | | TB0113Y | A004 | BJ | | 115-199 |
| 0460 | 22 | | GA | | 40-0 | 30-11-11 | | D03550 | | 6 | | D40570P | | 51 | | 001-099 |
| 0460 | 22 | | GA | | 41-0 | 30-11-11 | | D03550 | | 6 | | D40570P | | 51 | | 115-199 |
| 0461 | 22 | | GA | | 40-0 | 30-11-11 | | D03550 | | 3 | | D40570P | | 52 | | 001-099 |
| 0461 | 22 | | GA | | 41-0 | 30-11-11 | | D03550 | | 3 | | D40570P | | 52 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 40

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | | |
| 0462 | 22 | GA | | | 42-0 | 30-11-11 | D03550 | | 7 | | | D41380P | 21 | | | 001-099 |
| 0462 | 22 | GA | | | 43-0 | 30-11-11 | D03550 | | 7 | | | D41380P | 21 | | | 115-199 |
| 0463 | 22 | GA | | | 5-0 | 30-11-11 | D03550 | | 12 | | | GD00601 | DC.. | 2 | | 001-099 |
| 0463 | 22 | GA | | | 4-0 | 30-11-11 | D03550 | | 12 | | | GD00601 | DC.. | 2 | | 115-199 |
| 0464 | 22 | GA | | | 7-0 | 30-11-11 | D40570P | | 50 | | | D41380P | 20 | | | 001-099 |
| 0464 | 22 | GA | | | 9-0 | 30-11-11 | D40570P | | 50 | | | D41380P | 20 | | | 115-199 |
| 0465 | 24 | GK | | | 8-0 | 30-32-11 | D03706 | | 17 | | | SM00017 | | 9 | | 001-099 |
| 0465 | 24 | GK | | | 7-0 | 30-32-11 | D03706 | | 17 | | | SM00017 | | 9 | | 115-199 |
| 0466 | 24 | GK | | | 24-0 | 30-32-11 | D03706 | | 16 | | | D41414P | 54 | | | 001-099 |
| 0466 | 24 | GK | | | 25-0 | 30-32-11 | D03706 | | 16 | | | D41414P | 54 | | | 115-199 |
| 0467 | 22 | GA | | | 34-0 | 30-11-11 | D03706 | | 29 | | | D40570P | 39 | | | ALL |
| 0482 | 20 | GA | | | 5-0 | 26-23-11 | SM00018 | | | 9 | | D44102J | 3 | | | 001-099 |
| 0482 | 20 | GA | | | 7-0 | 26-23-11 | SM00018 | | | 9 | | D44102J | 3 | | | 115-199 |
| 0486 | 20 | GA | | | 29-0 | 27-41-31 | D40806J | | 46 | | | TB0100X | D002 | BJ | | 001-099 |
| 0486 | 20 | GA | | | 30-0 | 27-41-31 | D40806J | | 46 | | | TB0100X | D002 | BJ | | 115-199 |
| 0500 | 24 | GK | | | 7-0 | 33-13-31 | D40806J | | 9 | | | TB0115Y | A018 | BJ | | ALL |
| 0501 | 22 | GA | | | 8-0 | 33-16-52 | D03586 | | 4 | | | TB0116Z | 13 | BJ | | 001-099 |
| 0501 | 22 | GA | | | 7-0 | 33-16-52 | D03586 | | 4 | | | TB0116Z | 13 | BJ | | 115-199 |
| 0502 | 22 | GA | | | 15-0 | 33-16-61 | D41174J | | 12 | | | SM00012 | | 9 | | ALL |
| 0503 | 22 | GA | | | 4-0 | 33-16-61 | D41010P | | 8 | | | SM00012 | | 9 | | ALL |
| 0504 | 22 | GA | | | 18-0 | 33-16-61 | TB0058Y | C014 | BJ | | | SM00013 | | 9 | | 001-099 |
| 0504 | 22 | GA | | | 19-0 | 33-16-61 | TB0058Y | C014 | BJ | | | SM00013 | | 9 | | 115-199 |
| 0505 | 22 | GA | | | 4-0 | 33-16-61 | D41010P | | 7 | | | SM00013 | | 9 | | ALL |
| 0506 | 22 | GA | | | 11-0 | 33-16-62 | TB0116Y | A001 | BJ | | | SM00012 | | 9 | | ALL |
| 0507 | 22 | GA | | | 11-0 | 33-16-62 | TB0116Z | | 4 | BJ | | SM00013 | | 9 | | ALL |
| 0508 | 24 | GK | | | 40-0 | 36-11-31 | D03586 | | 1 | | | D40570P | 44 | | | ALL |
| 0509 | 24 | GK | | | 40-0 | 36-11-31 | D03586 | | 2 | | | D40570P | 45 | | | ALL |
| 0510 | 20 | GA | | | 30-0 | 27-21-11 | D40806J | | 16 | | | TB0158X | D003 | BJ | | 001-099 |
| 0510 | 20 | GA | | | 31-0 | 27-21-11 | D40806J | | 16 | | | TB0158X | D003 | BJ | | 115-199 |
| 0511 | 20 | GA | | | 42-0 | 27-21-11 | D40600P | | 27 | | | TB0158X | B003 | BJ | | 001-099 |
| 0511 | 20 | GA | | | 44-0 | 27-21-11 | D40600P | | 27 | | | TB0158X | B003 | BJ | | 115-199 |
| 0512 | 20 | GA | | | 42-0 | 27-21-11 | D40600P | | 28 | | | TB0158X | C003 | BJ | | 001-099 |
| 0512 | 20 | GA | | | 44-0 | 27-21-11 | D40600P | | 28 | | | TB0158X | C003 | BJ | | 115-199 |
| 0513 | 24 | GK | | | 7-0 | 28-25-11 | D03516 | | 9 | | | TB0112X | C004 | BJ | | 001-099 |
| 0513 | 22 | GA | | | 7-0 | 28-25-11 | D03516 | | 9 | | | TB0112X | C004 | BJ | | 115-199 |
| 0514 | 24 | GK | | | 7-0 | 28-25-11 | D03516 | | 8 | | | TB0112X | D004 | BJ | | 001-099 |
| 0514 | 22 | GA | | | 7-0 | 28-25-11 | D03516 | | 8 | | | TB0112X | D004 | BJ | | 115-199 |
| 0515 | 22 | GA | | | 6-0 | 24-33-12 | D03508 | | 34 | | | D40806J | 33 | | | 001-099 |
| 0516 | 22 | GA | | | 6-0 | 24-33-12 | D03508 | | 36 | | | D40806J | 43 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 41

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2078 | 286N2078 | | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | | |
| 0517 | 24 | | GK | | 5-0 | 24-33-11 | GD00600 | DC.. | 2 | | | D03508 | 32 | | | 001-099 | |
| 0517 | 20 | | GA | | 4-0 | 24-33-11 | D03508 | | 32 | | | GD00600 | DC.. | 2 | | 115-199 | |
| 0518 | 20 | | GA | | 5-0 | 24-33-12 | D03508 | | 35 | | | GD00600 | DC.. | 2 | | 001-099 | |
| 0519 | 24 | | GK | | 14-0 | 24-33-11 | D40296P | | 32 | | | D03508 | 6 | | | 001-099 | |
| 0519 | 22 | | GA | | 14-0 | 24-33-11 | D40296P | | 32 | | | D03508 | 6 | | | 115-199 | |
| 0520 | 24 | | GK | | 14-0 | 24-33-11 | D40296P | | 33 | | | D03508 | 33 | | | 001-099 | |
| 0520 | 22 | | GA | | 14-0 | 24-33-11 | D40296P | | 33 | | | D03508 | 33 | | | 115-199 | |
| 0525 | 24 | | GK | | 15-0 | 33-11-11 | D41174J | | 5 | | | SM00002 | | 9 | | 001-099 | |
| 0525 | 24 | | GK | | 16-0 | 33-11-11 | D41174J | | 5 | | | SM00002 | | 9 | | 115-199 | |
| 0529 | 22 | | GA | | 15-0 | 33-16-51 | TB0115Y | C017 | | BJ | | SM00003 | | 9 | | 001-099 | |
| 0529 | 22 | | GA | | 16-0 | 33-16-51 | SP01934 | | | 9 | | SM00003 | | 9 | | 115-199 | |
| 0530 | 22 | | GA | | 40-0 | SPARE | D40806J | | 7 | | | D40570P | 9 | | | 001-099 | |
| 0531 | 22 | | GA | | 23-0 | SPARE | D40600P | | 1 | | | D40570P | 11 | | | 001-099 | |
| 0532 | 24 | | GK | | 23-0 | SPARE | D40600P | | 5 | | | D40570P | 12 | | | 001-099 | |
| 0535 | 24 | | GK | | 22-0 | 33-14-11 | D41174J | | 30 | | | D41282P | 1 | | | 001-099 | |
| 0536 | 22 | | GA | | 5-0 | 33-14-11 | D41282P | | 2 | | | GD00608 | AC.. | 2 | | 001-099 | |
| 0537 | 24 | | GK | | 26-0 | 33-14-11 | D41280P | | 1 | | | D41878J | 25 | | | 001-099 | |
| 0538 | 22 | | GA | | 5-0 | 33-14-11 | D41280P | | 2 | | | GD00601 | AC.. | 2 | | 001-099 | |
| 0539 | 24 | | GK | | 4-0 | 33-11-21 | D41280P | | 4 | | | SM00019 | | 9 | | 001-099 | |
| 0540 | 24 | | GK | | 4-0 | 33-11-21 | D41282P | | 3 | | | SM00019 | | 9 | | 001-099 | |
| 0541 | 22 | | GA | | 5-0 | 33-11-21 | D41280P | | 3 | | | GD00600 | AC.. | 2 | | 001-099 | |
| 0542 | 22 | | GA | | 5-0 | 33-11-21 | D41282P | | 4 | | | GD00604 | AC.. | 2 | | 001-099 | |
| 0543 | 24 | | GK | | 4-0 | 33-11-31 | D41282P | | 5 | | | SM00021 | | 9 | | 001-099 | |
| 0544 | 22 | | GA | | 10-0 | 33-11-31 | D41282P | | 6 | | | GD00618 | AC.. | 2 | | 001-099 | |
| 0545 | 24 | | GK | | 4-0 | 33-11-31 | D41280P | | 5 | | | SM00021 | | 9 | | 001-099 | |
| 0546 | 22 | | GA | | 5-0 | 33-11-31 | D41280P | | 6 | | | GD00600 | AC.. | 2 | | 001-099 | |
| 0547 | 22 | | GA | | 5-0 | 33-11-31 | D41280P | | 7 | | | GD00602 | AC.. | 2 | | 001-099 | |
| 0548 | 24 | | GK | | 4-0 | 33-11-31 | D41280P | | 8 | | | TB0111X | D002 | BJ | | 001-099 | |
| 0549 | 22 | | GA | | 4-0 | 33-51-12 | D41280P | | 10 | | | TB0111X | C002 | BJ | | 001-099 | |
| 0551 | 20 | | GA | | 5-0 | 33-51-12 | D41280P | | 9 | | | GD00602 | DC.. | 2 | | 001-099 | |
| 0552 | 20 | | GA | | 23-0 | 28-22-31 | D41414P | | 49 | | | D41850P | 51 | | | 009-099 | |
| 0553 | 20 | | GA | | 7-0 | 28-22-31 | TB0115X | B001 | | BJ | | D03516 | 7 | | | 009-099 | |
| 0601 | 24 | | GK | | 30-0 | 28-22-31 | D03516 | | 11 | | | D41414P | 55 | | | 009-099 | |
| 0800 | 22 | | GA | | 11-0 | 24-51-72 | D40296P | | 11 | | | TB0116X | D017 | BJ | | ALL | |
| 0801 | 22 | | GA | | 27-0 | 34-22-83 | D40806J | | 7 | | | D41174J | 4 | | | 115-199 | |
| 1001 | 20 | | GE | CA | 27-0 | 33-13-12 | D02878 | | = A1 | | | D41878J | 10 | | | ALL | |
| 1001Z | | | | CA | 0-0 | 33-13-12 | D02878 | | = C1 | | | D41878J | 24 | | | ALL | |
| 2501B | 24 | | G2 | AA | 17-0 | 33-11-11 | D41878J | | 3 | | | D41010P | 14 | | | ALL | |
| 2501R | 24 | | G2 | AA | 0-0 | 33-11-11 | D41878J | | 4 | | | D41010P | 15 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 42

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | | To | | | | | Effectivity |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2078 | 286N2078 | | | FLT DECK TO E/E BAY CAT "S2A" SYSTEM (continued) | | | | | | | | | | | | |
| 2501Z | | | | AA | 0-0 | 33-11-11 | D41878J | | | | AA | D41010P | | | BB | ALL |
| 3001B | 24 | GM | BA | | 27-0 | 33-11-21 | D03501 | 7 | | | | D41174J | 19 | | | ALL |
| 3001R | 24 | GM | BA | | 0-0 | 33-11-21 | D03501 | 9 | | | | D41174J | 18 | | | ALL |
| 3001Y | 24 | GM | BA | | 0-0 | 33-11-21 | D03501 | 8 | | | | D41174J | 20 | | | ALL |
| 3003B | 22 | GC | AB | | 7-0 | 21-31-31 | D02346 | 5 | | | | TB0112X | D015 | BJ | | ALL |
| 3003R | 22 | GC | AB | | 0-0 | 21-31-31 | D02346 | 4 | | | | TB0112X | C016 | BJ | | ALL |
| 3003Y | 22 | GC | AB | | 0-0 | 21-31-31 | D02346 | 6 | | | | TB0112X | C015 | BJ | | ALL |
| 3502B | 24 | G3 | BB | | 17-0 | 33-11-11 | D41878J | 5 | | | | D41010P | 17 | | | ALL |
| 3502R | 24 | G3 | BB | | 0-0 | 33-11-11 | D41878J | 6 | | | | D41010P | 16 | | | ALL |
| 3502Y | 24 | G3 | BB | | 0-0 | 33-11-11 | D41878J | 7 | | | | D41010P | 18 | | | ALL |
| 3502Z | | | BB | | 0-0 | 33-11-11 | D41878J | | | | AA | D41010P | | | BB | ALL |
| FRAA | | | | | 0-0 | 33-11-11 | D41878J | | | | AA | D41878J | 39 | | | ALL |
| FRBB | | | | | 2-0 | 33-11-11 | GD01221 | ST.. | 2 | | | D41010P | | | BB | 001-099 |
| FRBB | | | | | 0-0 | 33-11-11 | GD01221 | ST.. | 2 | | | D41010P | | | BB | 115-199 |
| W2079 | 286N2079 | | | AIDS PRINTER, P14 TO E3-3 | | | | | | | | | | | | |
| 0001 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 1 | | | | D00779 | T | | | 115-199 |
| 0002 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 2 | | | | D00779 | U | | | 115-199 |
| 0003 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 3 | | | | D00779 | J | | | 115-199 |
| 0004 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 4 | | | | D00779 | L | | | 115-199 |
| 0005 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 5 | | | | D00779 | S | | | 115-199 |
| 0006 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 6 | | | | D00779 | H | | | 115-199 |
| 0007 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 7 | | | | D00779 | V | | | 115-199 |
| 0008 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 8 | | | | D00779 | N | | | 115-199 |
| 0009 | 22 | GA | | | 40-0 | 31-31-13 | D41523P | 9 | | | | D00779 | B | | | 115-199 |
| 0010 | 20 | GA | | | 3-0 | 31-31-13 | D00779 | C | | | | GD02397 | AC.. | 2 | | 115-199 |
| 0011 | 20 | GA | | | 3-0 | 31-31-13 | D00779 | E | | | | GD02397 | DC.. | 2 | | 115-199 |
| 0012 | 20 | GA | | | 3-0 | 31-31-13 | D00779 | P | | | | GD02397 | DC.. | 2 | | 115-199 |
| 0013 | 20 | GA | | | 3-0 | 31-31-13 | D00779 | F | | | | GD02397 | ST.. | 2 | | 115-199 |
| 0014 | 22 | GA | | | 19-0 | 31-31-13 | D00779 | A | | | | TB0121Y | C001 | BJ | | 115-199 |
| 1001 | 22 | GT | AA | | 40-0 | 31-31-13 | D41523P | 13 | | | | D00779 | R | | | 115-199 |
| 1001Z | | | AA | | 0-0 | 31-31-13 | D41523P | | | | AA | D00779 | | | AB | 115-199 |
| 1002 | 22 | GT | AB | | 40-0 | 31-31-13 | D41523P | 14 | | | | D00779 | D | | | 115-199 |
| 1002Z | | | AB | | 0-0 | 31-31-13 | D41523P | | | | AA | D00779 | | | AB | 115-199 |
| 1003 | 22 | GT | AC | | 40-0 | 31-31-13 | D41523P | 15 | | | | D00779 | G | | | 115-199 |
| 1003Z | | | AC | | 0-0 | 31-31-13 | D41523P | | | | AA | D00779 | | | AB | 115-199 |
| 5001B | 24 | G2 | AD | | 40-0 | 31-31-13 | D41523P | 11 | | | | D00779 | M | | | 115-199 |
| 5001R | 24 | G2 | AD | | 0-0 | 31-31-13 | D41523P | 10 | | | | D00779 | K | | | 115-199 |
| 5001Z | | | AD | | 0-0 | 31-31-13 | D41523P | 12 | | | | GD02397 | ST.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2070

Page 43

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | |
|------------|-------------|----|----|---------------------------------------|------|----------|---------|-------|------|------|--------|---------|-------------|------|------|---------|
| Wire No. | GA | CO | TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice |
| W2079 | 286N2079 | | | AIDS PRINTER, P14 TO E3-3 (continued) | | | | | | | | | | | | |
| FRAA | | | | | 0-0 | 31-31-13 | D41523P | | | | AA | D41523P | 16 | | | 115-199 |
| FRAB | | | | | 0-0 | 31-31-13 | D00779 | | | | AB | GD02397 | ST.. | 2 | | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W2070
Page 44 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2080 | 286N2080 | | | FLT DECK TO E/E BAY-CAT "A2" SYSTEM | | | | | | | | | | | |
| 0001 | 20 | | GA | | 48-0 | 24-22-41 | D03506 | | 6 | | D42368P | | 1 | | 001-099 |
| 0001 | 20 | | GA | | 47-0 | 24-22-41 | D03506 | | 6 | | D41868P | | 1 | | 115-199 |
| 0002 | 24 | | GK | | 48-0 | 24-22-41 | D03506 | | 20 | | D42368P | | 2 | | 001-099 |
| 0002 | 24 | | GK | | 47-0 | 24-22-41 | D03506 | | 20 | | D41868P | | 2 | | 115-199 |
| 0003 | 24 | | GK | | 42-0 | 24-22-41 | D03714 | | 20 | | D42368P | | 4 | | 001-003 |
| 0003 | 24 | | GK | | 42-0 | 24-22-41 | D03714 | | 20 | | D41868P | | 3 | | 115-199 |
| 0004 | 24 | | GK | | 42-0 | 24-22-41 | D03714 | | 8 | | D42368P | | 3 | | 001-003 |
| 0004 | 24 | | GK | | 42-0 | 24-22-41 | D03714 | | 8 | | D41868P | | 4 | | 115-199 |
| 0005 | 24 | | GK | | 31-0 | 24-22-41 | D03506 | | 14 | | TB0058X | C002 | BJ | | 001-099 |
| 0005 | 24 | | GK | | 29-0 | 24-22-41 | D03506 | | 14 | | TB0058X | C002 | BJ | | 115-199 |
| 0006 | 24 | | GK | | 17-0 | 24-22-41 | D03506 | | 13 | | D03714 | | 7 | | 001-003, 115-199 |
| 0007 | 24 | | GK | | 43-0 | 24-22-41 | TB0058X | B007 | BJ | | D42368P | | 6 | | 001-099 |
| 0007 | 24 | | GK | | 43-0 | 24-22-41 | TB0058X | B007 | BJ | | D41868P | | 5 | | 115-199 |
| 0008 | 24 | | GK | | 48-0 | 24-22-41 | D03506 | | 8 | | D42368P | | 5 | | 001-099 |
| 0008 | 24 | | GK | | 47-0 | 24-22-41 | D03506 | | 8 | | D41868P | | 6 | | 115-199 |
| 0009 | 22 | | GA | | 48-0 | 49-61-11 | D03576 | | 15 | | D40602P | | 1 | | 001-099 |
| 0009 | 22 | | GA | | 47-0 | 49-61-11 | D03576 | | 8 | | D40602P | | 1 | | 115-199 |
| 0010 | 22 | | GA | | 48-0 | 49-61-11 | D03576 | | 16 | | D40602P | | 2 | | 001-099 |
| 0010 | 22 | | GA | | 47-0 | 49-61-11 | D03576 | | 7 | | D40602P | | 2 | | 115-199 |
| 0011 | 22 | | GA | | 48-0 | 49-61-11 | D03576 | | 19 | | D40602P | | 3 | | 001-099 |
| 0011 | 22 | | GA | | 47-0 | 49-61-11 | D03576 | | 9 | | D40602P | | 3 | | 115-199 |
| 0012 | 22 | | GA | | 48-0 | 49-61-11 | D03576 | | 23 | | D40602P | | 4 | | 001-099 |
| 0012 | 22 | | GA | | 47-0 | 49-61-11 | D03576 | | 11 | | D40602P | | 4 | | 115-199 |
| 0013 | 22 | | GA | | 48-0 | 49-61-11 | D03576 | | 11 | | D40602P | | 5 | | 001-099 |
| 0013 | 22 | | GA | | 47-0 | 49-61-11 | D03576 | | 10 | | D40602P | | 5 | | 115-199 |
| 0014 | 24 | | GK | | 48-0 | 24-27-41 | TB0115Y | C005 | BJ | | D40602P | | 6 | | ALL |
| 0015 | 24 | | GK | | 48-0 | 24-27-41 | TB0115Y | C005 | BJ | | D41868P | | 7 | | 001-099 |
| 0015 | 24 | | GK | | 49-0 | 24-27-41 | TB0115Y | C005 | BJ | | D41868P | | 7 | | 115-199 |
| 0016 | 24 | | GK | | 47-0 | 24-27-41 | D03506 | | 1 | | D41868P | | 8 | | ALL |
| 0017 | 22 | | GA | | 8-0 | 29-22-11 | D03714 | | 4 | | GD00619 | DC.. | 2 | | 001-099 |
| 0017 | 22 | | GA | | 9-0 | 29-22-11 | D03714 | | 4 | | GD00619 | DC.. | 2 | | 115-199 |
| 0018 | 22 | | GA | | 8-3 | 29-22-11 | D03714 | | 1 | | TB0121X | A005 | BJ | | ALL |
| 0019 | 24 | | GK | | 6-0 | 36-11-41 | D03576 | | 22 | | TB0113X | A019 | BJ | | 001-099 |
| 0020 | 22 | | GA | | 8-0 | 24-27-41 | D03506 | | 10 | | TB0115Y | C005 | BJ | | 001-099 |
| 0020 | 22 | | GA | | 7-0 | 24-27-41 | D03506 | | 10 | | TB0115Y | C005 | BJ | | 115-199 |
| 0021 | 22 | | GA | | 4-0 | 24-27-41 | D03506 | | 2 | | GD00596 | DC.. | 2 | | ALL |
| 0022 | 20 | | GA | | 7-0 | 33-13-32 | D03576 | | 1 | | TB0115Z | | 7 | BJ | ALL |
| 0023 | 20 | | GA | | 7-0 | 33-13-32 | D03576 | | 2 | | TB0115Z | | 8 | BJ | ALL |
| 0024 | 22 | | GA | | 9-0 | 33-16-62 | D03576 | | 3 | | TB0116Z | | 4 | BJ | ALL |

WIRE LIST

D280N032

91-21-11

Section W2080

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2080 | 286N2080 | | | | FLT DECK TO E/E BAY-CAT "A2" SYSTEM (continued) | | | | | | | | | | | | |
| 0025 | 22 | | GA | | 9-0 | 33-16-52 | | D03576 | | | 4 | | TB0116Z | 14 | BJ | | ALL |
| 0026 | 22 | | GA | | 7-0 | 26-15-12 | | D03576 | | | 27 | | TB0115X | B004 | BJ | | 001-099 |
| 0026 | 22 | | GA | | 7-0 | 26-15-12 | | D03576 | | | 6 | | TB0115X | B004 | BJ | | 115-199 |
| 0027 | 22 | | GA | | 20-0 | SPARE | | D41868P | | | 21 | | D40602P | 14 | | | 115-199 |
| 0028 | 22 | | GA | | 20-0 | SPARE | | D41868P | | | 22 | | D40602P | 15 | | | 115-199 |
| 0029 | 22 | | GA | | 20-0 | SPARE | | D41868P | | | 23 | | D40602P | 9 | | | 115-199 |
| 0030 | 22 | | GA | | 20-0 | SPARE | | D41868P | | | 24 | | D40602P | 10 | | | 115-199 |
| 0031 | 22 | | GA | | 8-0 | 49-61-11 | | D03576 | | | 5 | | TB0115X | D001 | BJ | | 001-099 |
| 0031 | 22 | | GA | | 7-0 | 49-61-11 | | D03576 | | | 5 | | TB0115X | D001 | BJ | | 115-199 |
| 0032 | 20 | | GA | | 48-0 | SPARE | | D03576 | | CAP | Y | | D40602P | 7 | | | 001-099 |
| 0032 | 20 | | GA | | 47-0 | SPARE | | D03506 | | CAP | Y | | D40602P | 7 | | | 115-199 |
| 0033 | 20 | | GA | | 48-0 | SPARE | | D03576 | | CAP | Y | | D41868P | 9 | | | 001-099 |
| 0033 | 20 | | GA | | 47-0 | SPARE | | D03506 | | CAP | Y | | D41868P | 9 | | | 115-199 |
| 0034 | 20 | | GA | | 47-0 | SPARE | | D03576 | | CAP | Y | | D41868P | 10 | | | 115-199 |
| 0035 | 20 | | GA | | 48-0 | SPARE | | D03576 | | CAP | Y | | D40602P | 8 | | | 001-099 |
| 0035 | 20 | | GA | | 47-0 | SPARE | | D03576 | | CAP | Y | | D40602P | 8 | | | 115-199 |
| 0036 | 20 | | GA | | 42-0 | SPARE | | D03714 | | CAP | Y | | D40602P | 11 | | | ALL |
| 0037 | 20 | | GA | | 42-0 | SPARE | | D03714 | | CAP | Y | | D41868P | 11 | | | 115-199 |
| 0038 | 22 | | GA | | 8-3 | 29-22-11 | | D03714 | | | 15 | | TB0121X | A008 | BJ | | ALL |
| 0039 | 22 | | GA | | 8-3 | 29-22-11 | | D03714 | | | 14 | | TB0121X | B008 | BJ | | ALL |
| 0040 | 22 | | GA | | 8-3 | 29-22-11 | | D03714 | | | 16 | | TB0121X | C008 | BJ | | ALL |
| 0041 | 22 | | GA | | 8-3 | 29-22-11 | | D03714 | | | 24 | | TB0121Y | A023 | BJ | | ALL |
| 0042 | 22 | | GA | | 8-3 | 29-22-11 | | D03714 | | | 11 | | TB0121X | D008 | BJ | | ALL |
| 0043 | 22 | | GA | | 8-3 | 29-22-11 | | D03714 | | | 23 | | TB0121Y | C023 | BJ | | ALL |
| 0044 | 22 | | GA | | 8-3 | 29-22-11 | | D03714 | | | 2 | | TB0121X | B005 | BJ | | ALL |
| 0045 | 22 | | GA | | 8-3 | 29-22-11 | | D03714 | | | 3 | | TB0121X | C005 | BJ | | ALL |
| W2088 | 286N2088 | | | | JUMPER BUNDLE ENGINE BOTTLE 1 (RR ENGINE) | | | | | | | | | | | | |
| 0001R | 20 | | QZ | | 3-0 | 26-21-11 | | D42148J | | | 1 | | D02190 | 1 | | | ALL |
| 0002R | 20 | | QZ | | 3-0 | 26-21-11 | | D42148J | | | 2 | | D02190 | 2 | | | ALL |
| 0003R | 20 | | QZ | | 3-0 | 26-21-11 | | D42148J | | | 3 | | D02190 | 3 | | | ALL |
| 0004R | 20 | | QZ | | 2-0 | 26-21-11 | | D42148J | | | 4 | | D02188 | 1 | | | ALL |
| 0005R | 20 | | QZ | | 2-0 | 26-21-11 | | D42148J | | | 5 | | D02188 | 2 | | | ALL |
| 0006R | 20 | | QZ | | 2-0 | 26-21-11 | | D42148J | | | 6 | | D02188 | 5 | | | ALL |
| 0007R | 20 | | QZ | | 2-0 | 26-21-11 | | D42148J | | | 7 | | D42148J | 8 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2080

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number GA CO TY | | | Fam | Description FT-IN Diagram | | From Equip Term Type Splice | | | | To Equip Term Type Splice | | | | Effectivity | |
|------------------------|-------------------------|--|----|-----|---|----------|--------------------------------|--|---|--|------------------------------|---------|--|---|-------------|-----|
| | | | | | | | | | | | | | | | | |
| W2090 | 286N2090 | | | | JUMPER BUNDLE ENGINE BOTTLE 2 (RR ENGINE) | | | | | | | | | | | |
| 0001R | 20 | | QZ | | 3-0 | 26-21-11 | D42150J | | 1 | | | D02266 | | 1 | | ALL |
| 0002R | 20 | | QZ | | 3-0 | 26-21-11 | D42150J | | 2 | | | D02266 | | 2 | | ALL |
| 0003R | 20 | | QZ | | 3-0 | 26-21-11 | D42150J | | 3 | | | D02266 | | 3 | | ALL |
| 0004R | 20 | | QZ | | 3-0 | 26-21-11 | D42150J | | 4 | | | D02268 | | 1 | | ALL |
| 0005R | 20 | | QZ | | 3-0 | 26-21-11 | D42150J | | 5 | | | D02268 | | 2 | | ALL |
| 0006R | 20 | | QZ | | 3-0 | 26-21-11 | D42150J | | 6 | | | D02268 | | 5 | | ALL |
| 0007R | 20 | | QZ | | 2-0 | 26-21-11 | D42150J | | 7 | | | D42150J | | 8 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2090

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2134 | 286N2134 | | | | P8-APU FIRE & FIRE TEST PNL TO P54 | | | | | | | | | | |
| 0001 | 22 | | GA | | 4-11 | 26-15-11 | D00560 | | | | TB0158A | A007 | 2 | | 001-099 |
| 0001 | 22 | | GA | | 7-0 | 26-15-11 | D00560 | | | | TB0158A | A007 | 2 | | 115-199 |
| 0002 | 22 | | GA | | 27-11 | 26-15-11 | D00560 | | | | D40946P | | 1 | | 001-099 |
| 0002 | 22 | | GA | | 28-0 | 26-15-11 | D00560 | | | | D40946P | | 1 | | 115-199 |
| 0003 | 22 | | GA | | 4-11 | 26-15-11 | D00560 | | | | TB0158A | A006 | 2 | | 001-099 |
| 0003 | 22 | | GA | | 7-0 | 26-15-11 | D00560 | | | | TB0158A | A006 | 2 | | 115-199 |
| 0004 | 22 | | GA | | 27-11 | 26-15-12 | D00560 | | | | D40946P | | 3 | | 001-099 |
| 0004 | 22 | | GA | | 28-0 | 26-15-12 | D00560 | | | | D40946P | | 3 | | 115-199 |
| 0005 | 22 | | GA | | 27-11 | 26-15-12 | D00560 | | | | D40946P | | 4 | | 001-099 |
| 0005 | 22 | | GA | | 28-0 | 26-15-12 | D00560 | | | | D40946P | | 4 | | 115-199 |
| 0006 | 20 | | GA | | 0-7 | 26-22-21 | D00560 | | | | SM00001 | | 9 | | 001-099 |
| 0006 | 20 | | GA | | 0-6 | 26-22-21 | D00560 | | | | SM00001 | | 9 | | 115-199 |
| 0007 | 20 | | GA | | 4-11 | 26-22-21 | D00560 | | | | TB0058Y | C005 | BJ | | 001-099 |
| 0007 | 20 | | GA | | 7-0 | 26-22-21 | D00560 | | | | TB0058Y | C005 | BJ | | 115-199 |
| 0008 | 20 | | GA | | 4-11 | 26-22-21 | D00560 | | | | TB0058Y | C005 | BJ | | 001-099 |
| 0008 | 20 | | GA | | 7-0 | 26-22-21 | D00560 | | | | TB0058Y | C005 | BJ | | 115-199 |
| 0009 | 20 | | GA | | 0-7 | 26-22-21 | D00560 | | | | SM00001 | | 9 | | 001-099 |
| 0009 | 20 | | GA | | 0-6 | 26-22-21 | D00560 | | | | SM00001 | | 9 | | 115-199 |
| 0011 | 20 | | GA | | 28-0 | 26-22-21 | D40946P | | | | SM00001 | | 9 | | 115-199 |
| 0012 | 20 | | GA | | 30-0 | 26-22-21 | D40946P | | | | TB0058Y | C005 | BJ | | 115-199 |
| 0013 | 24 | | GK | | 4-11 | 24-22-41 | D00560 | | | | TB0058X | C002 | BJ | | 001-099 |
| 0013 | 24 | | GK | | 7-0 | 24-22-41 | D00560 | | | | TB0058X | C002 | BJ | | 115-199 |
| 0014 | 24 | | GK | | 4-11 | 24-22-41 | D00560 | | | | TB0058X | B007 | BJ | | 001-099 |
| 0014 | 24 | | GK | | 7-0 | 24-22-41 | D00560 | | | | TB0058X | B007 | BJ | | 115-199 |
| 0015 | 24 | | GK | | 4-11 | 36-11-41 | D00560 | | | | TB0058X | A002 | BJ | | 001-099 |
| 0015 | 24 | | GK | | 7-0 | 36-11-41 | D00560 | | | | TB0058X | A002 | BJ | | 115-199 |
| 0016 | 24 | | GK | | 4-11 | 36-11-41 | D00560 | | | | TB0058X | D012 | BJ | | 001-099 |
| 0016 | 24 | | GK | | 7-0 | 36-11-41 | D00560 | | | | TB0058X | D012 | BJ | | 115-199 |
| 0017 | 22 | | GA | | 4-11 | 28-25-21 | D00560 | | | | TB0158X | A003 | BJ | | 001-099 |
| 0017 | 22 | | GA | | 7-0 | 28-25-21 | D00560 | | | | TB0158X | A003 | BJ | | 115-199 |
| 0018 | 22 | | GA | | 27-11 | 28-25-21 | D00560 | | | | D40946P | | 11 | | 001-099 |
| 0018 | 22 | | GA | | 28-0 | 28-25-21 | D00560 | | | | D40946P | | 11 | | 115-199 |
| 0019 | 22 | | GA | | 4-11 | 28-25-21 | D00560 | | | | TB0058X | A012 | BJ | | 001-099 |
| 0019 | 22 | | GA | | 7-0 | 28-25-21 | D00560 | | | | TB0058X | A012 | BJ | | 115-199 |
| 0020 | 22 | | GA | | 4-11 | 49-61-11 | D00560 | | | | TB0058X | B011 | BJ | | 001-099 |
| 0020 | 22 | | GA | | 7-0 | 49-61-11 | D00560 | | | | TB0058X | B011 | BJ | | 115-199 |
| 0021 | 22 | | GA | | 4-11 | 49-61-11 | D00560 | | | | TB0058X | C011 | BJ | | 001-099 |
| 0021 | 22 | | GA | | 7-0 | 49-61-11 | D00560 | | | | TB0058X | C011 | BJ | | 115-199 |
| 0022 | 22 | | GA | | 4-11 | 49-61-11 | D00560 | | | | TB0058X | D011 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2130

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2134 | 286N2134 | | | P8-APU FIRE & FIRE TEST PNL TO P54 (continued) | | | | | | | | | | | |
| 0022 | 22 | | GA | | 7-0 | 49-61-11 | D00560 | | 7 | | TB0058X | D011 | BJ | | 115-199 |
| 0023 | 20 | | GA | | 4-11 | 31-51-33 | D00560 | | 17 | | GD00742 | DC.. | 2 | | 001-099 |
| 0023 | 20 | | GA | | 7-0 | 31-51-33 | D00560 | | 17 | | GD00742 | DC.. | 2 | | 115-199 |
| 0024 | 22 | | GA | | 27-11 | 31-51-33 | D00560 | | 34 | | D40946P | | 16 | | 001-099 |
| 0024 | 22 | | GA | | 28-0 | 31-51-33 | D00560 | | 34 | | D40946P | | 16 | | 115-199 |
| 0025 | 22 | | GA | | 4-11 | 33-16-61 | D00560 | | 1 | | TB0058Y | C014 | BJ | | 001-099 |
| 0025 | 22 | | GA | | 7-0 | 33-16-61 | D00560 | | 1 | | TB0058Y | C014 | BJ | | 115-199 |
| 0026 | 22 | | GA | | 27-11 | 26-16-11 | D03494 | | 3 | | D40946P | | 9 | | 001-099 |
| 0026 | 22 | | GA | | 28-0 | 26-16-11 | D03494 | | 3 | | D40946P | | 9 | | 115-199 |
| 0027 | 22 | | GA | | 4-11 | 26-16-11 | D03494 | | 4 | | GD00742 | DC.. | 2 | | 001-099 |
| 0027 | 20 | | GA | | 8-0 | 26-16-11 | D03494 | | 4 | | GD00742 | DC.. | 2 | | 115-199 |
| 0028 | 22 | | GA | | 27-11 | 26-15-11 | D40946P | | 8 | | D03494 | | 1 | | 001-099 |
| 0028 | 22 | | GA | | 28-0 | 26-15-11 | D03494 | | 1 | | D40946P | | 8 | | 115-199 |
| 0029 | 22 | | GA | | 4-11 | 26-15-11 | D03494 | | 2 | | GD00742 | DC.. | 2 | | 001-099 |
| 0029 | 22 | | GA | | 8-0 | 26-15-11 | D03494 | | 2 | | GD00742 | DC.. | 2 | | 115-199 |
| 0030 | 22 | | GA | | 27-6 | 26-15-11 | D40946P | | 2 | | TB0158A | C006 | 2 | | 001-099 |
| 0030 | 22 | | GA | | 28-0 | 26-15-11 | D40946P | | 2 | | TB0158A | C006 | 2 | | 115-199 |
| 0031 | 22 | | GA | | 4-11 | 26-15-11 | D00560 | | 24 | | GD00742 | ST.. | 2 | | 001-099 |
| 0031 | 22 | | GA | | 7-0 | 26-15-11 | D00560 | | 24 | | GD00742 | ST.. | 2 | | 115-199 |
| 0033 | 22 | | GA | | 0-7 | 26-15-11 | TB0158A | | C006 | 2 | TB0158A | C007 | 2 | | 001-099 |
| 0033 | 22 | | GA | | 1-0 | 26-15-11 | TB0158A | | C006 | 2 | TB0158A | C007 | 2 | | 115-199 |
| 0034 | 20 | | GA | | 27-11 | 26-22-21 | D40946P | | 6 | | SM00001 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2130

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|----|-------------|--|----------|---------|-------|------|------|--------|-------|-------------|------|---------|
| Wire No. | GA | CO | TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W2142 | 286N2142 | | | | P37 TO R. MAIN PITOT PROBE & R. AOA SNSR | | | | | | | | | | |
| 0001 | 20 | | GA | | 35-8 | 30-31-12 | D40862P | | 1 | | D02762 | | = A | | 115-199 |
| 0002 | 20 | | GA | | 35-8 | 30-31-12 | D40862P | | 2 | | D02762 | | = B | | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W2140
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------|-------------|----|-------|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2150 | 286N2150 | | | | NOSE W/W DISC TO P33,APU REMOTE CONTROL | | | | | | | | | | | |
| 0001 | 20 | GA | | | 30-0 | 26-15-12 | D40162J | | 1 | | | D41096P | 1 | | | ALL |
| 0002 | 20 | GA | | | 30-0 | SPARE | D40162J | | 8 | | | D41096P | 8 | | | 001-099 |
| 0003 | 20 | GA | | | 30-0 | 26-15-12 | D40162J | | 3 | | | D41096P | 3 | | | ALL |
| 0004 | 20 | GA | | | 30-0 | 26-15-12 | D40162J | | 4 | | | D41096P | 4 | | | ALL |
| 0005 | 20 | GA | | | 5-0 | 26-15-12 | D40162J | | 5 | | | GD00743 | DC.. | E | | ALL |
| 0006 | 20 | GA | | | 30-0 | 26-15-12 | D40162J | | 6 | | | D41096P | 6 | | | ALL |
| 0007 | 20 | GA | | | 30-0 | SPARE | D40162J | | 22 | | | D41096P | 22 | | | 001-099 |
| 0008 | 20 | GA | | | 30-0 | 26-22-21 | D40162J | | 9 | | | D41096P | 9 | | | 001-099 |
| 0008 | 20 | GA | | | 30-0 | 26-15-12 | D40162J | | 9 | | | D41096P | 9 | | | 115-199 |
| 0009 | 20 | GA | | | 30-0 | SPARE | D40162J | | 12 | | | D41096P | 12 | | | 001-099 |
| 0009 | 20 | GA | | | 30-0 | 32-44-11 | D40162J | | 16 | | | D41096P | 8 | | | 115-199 |
| 0010 | 20 | GA | | | 5-0 | 32-44-11 | D40162J | | 10 | | | GD00743 | DC.. | E | | 115-199 |
| 0011 | 20 | GA | | | 30-0 | 32-44-11 | D40162J | | 22 | | | D41096P | 5 | | | 115-199 |
| 0012 | 20 | GA | | | 10-0 | 32-35-11 | D04360 | | 3 | | | D41096P | 11 | | | 001-099 |
| 0012 | 20 | GA | | | 11-0 | 32-35-11 | D04360 | | 3 | | | D41096P | 11 | | | 115-199 |
| 0013 | 20 | GA | | | 10-0 | 32-35-11 | D04360 | | 2 | | | D41096P | 10 | | | 001-099 |
| 0013 | 20 | GA | | | 11-0 | 32-35-11 | D04360 | | 2 | | | D41096P | 10 | | | 115-199 |
| 0014 | 18 | GA | | | 42-0 | 32-12-12 | SP01110 | | 9 | | | SP01100 | | 9 | | 001-099 |
| 0014 | 18 | GA | | | 34-0 | 32-12-12 | SP01110 | | 9 | | | SP01100 | | 9 | | 115-199 |
| 0020 | 20 | GA | | | 5-0 | 26-15-12 | D40162J | | 24 | | | GD00743 | DC.. | E | | 001-099 |
| 0021 | 18 | GA | | | 7-0 | 32-12-12 | L00489 | | CTR | BK | | SP01108 | | 9 | | 001-099 |
| 0021 | 18 | GA | | | 6-0 | 32-12-12 | L00489 | | CTR | BK | | SP01108 | | 9 | | 115-199 |
| 0022 | 18 | GA | | | 8-0 | 32-12-12 | L00489 | | GND | C | | GD02518 | DC.. | E | | 001-099 |
| 0022 | 18 | GA | | | 7-0 | 32-12-12 | L00489 | | GND | C | | GD02518 | DC.. | E | | 115-199 |
| 0023 | 18 | GA | | | 20-0 | 32-12-12 | D41096P | | 2 | 18 | | SP01236 | | 9 | | 001-099 |
| 0023 | 18 | GA | | | 27-0 | 32-12-12 | D41096P | | 2 | 18 | | SP01236 | | 9 | | 115-199 |
| 0024 | 18 | GA | | | 20-0 | 32-12-12 | D41096P | | 7 | 18 | | SP01238 | | 9 | | 001-099 |
| 0024 | 18 | GA | | | 27-0 | 32-12-12 | D41096P | | 7 | 18 | | SP01238 | | 9 | | 115-199 |
| 0025 | 20 | GA | | | 39-0 | 32-12-12 | D40162J | | 2 | | | SP01102 | | 9 | | 115-199 |
| 0026 | 20 | GA | | | 39-0 | 32-12-12 | D40162J | | 7 | | | SP01104 | | 9 | | 115-199 |
| 2501B | 20 | GF | AA | | 40-0 | 32-12-12 | D40162J | | 7 | | | SP01104 | | 9 | | 001-099 |
| 2501B | 20 | GF | AA | | 37-0 | 23-71-11 | D40162J | | 11 | | | SP00067 | | 9 | | 115-199 |
| 2501R | 20 | GF | AA | | 0-0 | 32-12-12 | D40162J | | 2 | | | SP01102 | | 9 | | 001-099 |
| 2501R | 20 | GF | AA | | 0-0 | 23-71-11 | D40162J | | 12 | | | SP00065 | | 9 | | 115-199 |
| 2501Z | | | AA | | 0-0 | 32-12-12 | D40162J | | DED | | | SP01102 | DED | | | 001-099 |
| 2501Z | | | AA | | 0-0 | 23-71-11 | D40162J | | 13 | | | SP00069 | | 9 | | 115-199 |
| 2502B | 20 | GF | AB | | 37-0 | 23-71-11 | D40162J | | 17 | | | SP00057 | | 9 | | 115-199 |
| 2502R | 20 | GF | AB | | 0-0 | 23-71-11 | D40162J | | 18 | | | SP00059 | | 9 | | 115-199 |
| 2502Z | | | AB | | 0-0 | 23-71-11 | D40162J | | 19 | | | SP00061 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2150

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|------|------|--------|-------------|------|---|--|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W2150 | 286N2150 | | | | NOSE W/W DISC TO P33,APU REMOTE CONTROL (continued) | | | | | | | | | | | | | | |
| A-01 | | | | | 0-0 | 32-12-12 | | S10362 | | | | 1 | | | SP01100 | | 9 | | ALL |
| A-02 | | | | | 0-0 | 32-12-12 | | S10362 | | | | 2 | | | SP01102 | | 9 | | ALL |
| A-03 | | | | | 0-0 | 32-12-12 | | S10362 | | | | 3 | | | SP01104 | | 9 | | ALL |
| A-04 | | | | | 0-0 | 32-12-12 | | S10362 | | | | 4 | | | SP01102 | CAP | Y | | ALL |
| A-05 | | | | | 0-0 | 32-12-12 | | S10362 | | | | 5 | | | SP01102 | CAP | Y | | ALL |
| A-06 | | | | | 0-0 | 32-12-12 | | S10362 | | | | 6 | | | SP01102 | CAP | Y | | ALL |
| B-01 | | | | | 0-0 | 32-12-12 | | S10372 | | | | 1 | | | SP01102 | | 9 | | ALL |
| B-02 | | | | | 0-0 | 32-12-12 | | S10372 | | | | 2 | | | SP01108 | | 9 | | ALL |
| B-03 | | | | | 0-0 | 32-12-12 | | S10372 | | | | 3 | | | SP01238 | CAP | Y | | 001-099 |
| B-03 | | | | | 0-0 | 32-12-12 | | S10372 | | | | 3 | | | SP01108 | CAP | Y | | 115-199 |
| B-04 | | | | | 0-0 | 32-12-12 | | S10372 | | | | 4 | | | SP01238 | | 9 | | ALL |
| B-05 | | | | | 0-0 | 32-12-12 | | S10372 | | | | 5 | | | SP01238 | CAP | Y | | 001-099 |
| B-05 | | | | | 0-0 | 32-12-12 | | S10372 | | | | 5 | | | SP01108 | CAP | Y | | 115-199 |
| B-06 | | | | | 0-0 | 32-12-12 | | S10372 | | | | 6 | | | SP01236 | | 9 | | ALL |
| W2152 | 286N2152 | | | | P36,E/E BAY TO NOSE GEAR WHEELWELL DISC. | | | | | | | | | | | | | | |
| 0001 | 16 | | GA | | 9-0 | 33-42-21 | | D40388J | | A | | | | | GD00031 | ST.. | E | | 001-099 |
| 0001 | 16 | | GA | | 8-0 | 33-42-21 | | D40388J | | A | | | | | GD00031 | ST.. | E | | 115-199 |
| 0002 | 18 | | GA | | 20-0 | 33-31-11 | | L00071 | =P | C | | * | | | L00078 | =P | C | | 001-099 |
| 0002 | 18 | | GA | | 19-0 | 33-31-11 | | L00071 | =P | C | | * | | | L00078 | =P | C | | 115-199 |
| 0003 | 18 | | GA | | 17-0 | 33-31-11 | | L00071 | =G | E | | | | | GD01627 | DC.. | E | | ALL |
| 0004 | 18 | | GA | | 5-0 | 33-31-11 | | L00078 | =G | E | | | | | GD01627 | DC.. | E | | 001-099 |
| 0004 | 18 | | GA | | 4-0 | 33-31-11 | | L00078 | =G | E | | | | | GD01627 | DC.. | E | | 115-199 |
| 0005 | 18 | | GA | | 23-0 | 33-42-21 | | D40388J | | B | | | | | D40390P | | 1 | | 001-099 |
| 0005 | 18 | | GA | | 24-0 | 33-42-21 | | D40388J | | B | | | | | D40390P | | 1 | | 115-199 |
| 0006 | 18 | | GA | | 26-0 | 33-31-11 | | L00071 | =P | C | | * | | | D40388J | | C | | 001-099 |
| 0006 | 18 | | GA | | 29-0 | 33-31-11 | | L00071 | =P | C | | * | | | D40388J | | C | | 115-199 |
| 0007 | 18 | | GA | | 23-0 | 33-31-11 | | D40388J | | D | | | | | D40390P | | 2 | | 001-099 |
| 0007 | 18 | | GA | | 24-0 | 33-31-11 | | D40388J | | D | | | | | D40390P | | 2 | | 115-199 |
| 0008 | 18 | | GA | | 41-0 | 32-12-12 | | D40388J | | E | | | | | D02454 | | 1 | | 001-099 |
| 0008 | 18 | | GA | | 43-0 | 32-12-12 | | D40388J | | E | | | | | D02454 | | 1 | | 115-199 |
| 0009 | 18 | | GA | | 11-0 | 32-12-12 | | D02454 | | 3 | | | | | GD01628 | ST.. | E | | 001-099 |
| 0009 | 18 | | GA | | 10-0 | 32-12-12 | | D02454 | | 3 | | | | | GD01628 | ST.. | E | | 115-199 |
| 0010 | 18 | | GA | | 11-0 | 32-12-12 | | D02454 | | 2 | | | | | GD02518 | DC.. | E | | 001-099 |
| 0010 | 18 | | GA | | 10-0 | 32-12-12 | | D02454 | | 2 | | | | | GD02518 | DC.. | E | | 115-199 |
| 0011 | 20 | | GA | | 33-0 | 32-12-12 | | D40388J | | G | | | | | D41650P | | 6 | | 001-099 |
| 0011 | 18 | | GA | | 33-0 | 32-12-12 | | D40388J | | G | | | | | D41650P | | 6 | | 115-199 |
| 0012 | 18 | | GA | | 23-0 | 33-42-11 | | D40388J | | H | | | | | D40390P | | 3 | | 001-099 |
| 0012 | 18 | | GA | | 24-0 | 33-42-11 | | D40388J | | H | | | | | D40390P | | 3 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2150

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2152 | 286N2152 | | | P36,E/E BAY TO NOSE GEAR WHEELWELL DISC. (continued) | | | | | | | | | | | |
| 0013 | 12 | | GA | | 9-0 | 33-42-11 | D40388J | | P | | GD00031 | ST.. | E | | 001-099 |
| 0013 | 12 | | GA | | 7-2 | 33-42-11 | D40388J | | P | | GD00031 | ST.. | E | | 115-199 |
| 0016 | 12 | | GA | | 9-0 | 33-42-11 | D40388J | | R | | GD00030 | AC.. | E | | 001-099 |
| 0016 | 12 | | GA | | 7-2 | 33-42-11 | D40388J | | R | | GD00030 | AC.. | E | | 115-199 |
| 0017 | 16 | | GA | | 9-0 | 33-42-21 | D40388J | | K | | GD00030 | AC.. | E | | 001-099 |
| 0017 | 16 | | GA | | 8-0 | 33-42-21 | D40388J | | K | | GD00030 | AC.. | E | | 115-199 |
| 0018 | 20 | | GA | | 37-0 | 23-43-11 | B00060 | | =P | C | TB0116X | C015 | BJ | | 001-099 |
| 0018 | 20 | | GA | | 39-0 | 23-43-11 | B00060 | | =P | C | TB0116X | C015 | BJ | | 115-199 |
| 0019 | 20 | | GA | | 32-0 | 23-43-11 | B00060 | | =G | C | GD00032 | DC.. | E | | 001-099 |
| 0019 | 20 | | GA | | 35-0 | 23-43-11 | B00060 | | =G | C | GD00032 | DC.. | E | | 115-199 |
| 0020 | 18 | | GA | | 24-0 | SPARE | D40388J | | L | | D40390P | | 5 | | 115-199 |
| 0021 | 20 | | GA | | 33-0 | 32-12-12 | D40388J | | F | | D41650P | | 5 | | 001-099 |
| 0021 | 18 | | GA | | 33-0 | 32-12-12 | D40388J | | F | | D41650P | | 5 | | 115-199 |
| 0022 | 18 | | GA | | 37-0 | SPARE | D40388J | | N | | SP01104 | CAP | Y | | 115-199 |
| 0023 | 18 | | GA | | 37-0 | SPARE | D40388J | | O | | SP01108 | CAP | Y | | 115-199 |
| 0030 | 18 | | GA | | 23-0 | 33-42-12 | D40388J | | W | | D40390P | | 4 | | 001-099 |
| 0031 | 12 | | GA | | 9-0 | 33-42-12 | D40388J | | S | | GD00030 | AC.. | E | | 001-099 |
| 0032 | 12 | | GA | | 9-0 | 33-42-12 | D40388J | | T | | GD00031 | ST.. | E | | 001-099 |
| 0033 | 20 | | GA | | 23-0 | SPARE | D40388J | | L | | D40390P | | 6 | | 001-099 |
| 0034 | 20 | | GA | | 23-0 | 33-42-31 | D40388J | | M | | D40390P | | 7 | | 001-099 |
| 2001B | 20 | | GB | AA | 31-0 | 32-61-22 | SP00040 | | | 9 | D41650P | | 2 | | 001-099 |
| 2001B | 20 | | GB | AA | 33-0 | 32-61-22 | SP00040 | | | 9 | D41650P | | 2 | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 32-61-22 | SP00042 | | | 9 | D41650P | | 9 | | ALL |
| 2002B | 20 | | GB | AB | 36-0 | 32-61-22 | SP00044 | | | 9 | D41650P | | 4 | | 001-099 |
| 2002B | 20 | | GB | AB | 38-0 | 32-61-22 | SP00044 | | | 9 | D41650P | | 4 | | 115-199 |
| 2002R | 20 | | GB | AB | 0-0 | 32-61-22 | SP00046 | | | 9 | D41650P | | 3 | | ALL |
| 2003B | 20 | | GB | AC | 33-0 | 32-09-11 | D40388J | | I | | D41650P | | 7 | | 001-099 |
| 2003B | 18 | | GB | AC | 33-0 | 32-09-11 | D40388J | | I | | D41650P | | 7 | | 115-199 |
| 2003R | 20 | | GB | AC | 0-0 | 32-09-11 | D40388J | | J | | D41650P | | 8 | | 001-099 |
| 2003R | 18 | | GB | AC | 0-0 | 32-09-11 | D40388J | | J | | D41650P | | 8 | | 115-199 |
| 2004B | 20 | | GB | AD | 36-0 | 32-61-13 | D41650P | | | 10 | SP01978 | | 9 | | 001-099 |
| 2004B | 20 | | GB | AD | 37-0 | 32-61-13 | D41650P | | | 10 | SP01978 | | 9 | | 115-199 |
| 2004R | 20 | | GB | AD | 0-0 | 32-61-13 | D41650P | | | 11 | SP01976 | | 9 | | ALL |
| 2005B | 20 | | GB | AE | 39-0 | 32-61-13 | D41650P | | | 12 | SP01982 | | 9 | | 001-099 |
| 2005B | 20 | | GB | AE | 46-0 | 32-61-13 | D41650P | | | 12 | SP01982 | | 9 | | 115-199 |
| 2005R | 20 | | GB | AE | 0-0 | 32-61-13 | D41650P | | | 13 | SP01980 | | 9 | | ALL |
| A-A | | | | | 0-0 | 32-61-22 | S10066 | | BLU | | SP00044 | | 9 | | ALL |
| A-B | | | | | 0-0 | 32-61-22 | S10066 | | RED | | SP00046 | | 9 | | ALL |
| A-C | | | | | 0-0 | 32-61-22 | S10065 | | BLU | | SP00040 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2150

Page 3

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2150
Page 4
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2156 | | 286N2156 | | | | FLIGHT DECK TO E/E BAY CAT "S2B" SYSTEM (continued) | | | | | | | | | |
| 0028 | 20 | GA | | | 2-0 | 21-33-11 | GD01766 | ST.. | E | | D02694 | 5 | | | ALL |
| 0030 | 24 | GK | | | 29-0 | 21-58-11 | D01574 | 5 | | | D41060P | 1 | | | ALL |
| 0031 | 24 | GK | | | 40-0 | 21-58-11 | TB0111Y | A009 | BJ | | D41060P | 2 | | | ALL |
| 0032 | 20 | GA | | | 39-0 | 21-58-11 | TB0113X | D002 | BJ | | D41060P | 3 | | | ALL |
| 0033 | 20 | GA | | | 29-0 | 21-58-11 | D01574 | 1 | | | D41060P | 4 | | | ALL |
| 0034 | 24 | GK | | | 29-0 | 21-58-11 | D01574 | 2 | | | D41060P | 5 | | | ALL |
| 0035 | 20 | GA | | | 3-0 | 21-58-11 | D01574 | 3 | | | GD00128 | DC.. | E | | ALL |
| 0036 | 20 | GA | | | 3-0 | 21-58-11 | D01574 | 4 | | | GD00129 | ST.. | E | | ALL |
| 0038 | 24 | GK | | | 39-0 | 21-58-12 | D03518 | 16 | | | D41060P | 7 | | | ALL |
| 0042 | 20 | GA | | | 38-0 | 74-31-21 | D03530 | 5 | | | D41858P | 31 | | | ALL |
| 0043 | 20 | GA | | | 38-0 | 74-31-21 | D03530 | 6 | | | D41858P | 30 | | | ALL |
| 0044 | 24 | GK | | | 39-0 | 21-58-12 | D03518 | 19 | | | D41060P | 18 | | | ALL |
| 0045 | 20 | GA | | | 5-0 | 30-21-11 | D03530 | 14 | | | GD00596 | DC.. | 2 | | ALL |
| 0046 | 20 | GA | | | 45-0 | 27-61-12 | D03562 | 2 | | | D41838P | 4 | | | ALL |
| 0048 | 20 | GA | | | 39-0 | 74-31-11 | D03530 | 9 | | | D41060P | 33 | | | ALL |
| 0049 | 20 | GA | | | 39-0 | 74-31-11 | D03530 | 10 | | | D41060P | 39 | | | ALL |
| 0050 | 22 | GA | | | 37-0 | 35-21-11 | D04802 | 8 | | | D41858P | 8 | | | 001-099 |
| 0050 | 20 | GA | | | 37-0 | 35-21-11 | D04802 | 8 | | | D41858P | 8 | | | 115-199 |
| 0051 | 24 | GK | | | 37-0 | 35-21-11 | D04802 | 9 | | | D41858P | 9 | | | 001-099 |
| 0051 | 22 | GA | | | 37-0 | 35-21-11 | D04802 | 9 | | | D41858P | 9 | | | 115-199 |
| 0052 | 22 | GA | | | 3-0 | 35-21-11 | D04802 | 10 | | | GD00596 | DC.. | 2 | | 001-099 |
| 0052 | 24 | GK | | | 3-0 | 35-21-11 | D04802 | 10 | | | GD00596 | DC.. | 2 | | 115-199 |
| 0053 | 20 | GA | | | 6-0 | 33-13-31 | D04802 | 1 | | | TB0114Z | 7 | BJ | | ALL |
| 0054 | 20 | GA | | | 6-0 | 33-13-31 | D04802 | 2 | | | TB0114Z | 9 | BJ | | ALL |
| 0055 | 22 | GA | | | 6-0 | 33-16-52 | D04802 | 4 | | | TB0114Z | 21 | BJ | | ALL |
| 0056 | 22 | GA | | | 7-0 | 33-16-52 | D04802 | 3 | | | TB0116Z | 13 | BJ | | ALL |
| 0057 | 22 | GA | | | 38-0 | 30-21-11 | D03530 | 13 | | | D41858P | 29 | | | ALL |
| 0059 | 24 | GK | | | 10-0 | 24-33-12 | D40808J | 3 | | | D41904P | 4 | | | 001-099 |
| 0064 | 22 | GA | | | 35-0 | 26-11-11 | D40808J | 16 | | | D41060P | 37 | | | ALL |
| 0066 | 22 | GA | | | 34-0 | 26-11-21 | D40808J | 7 | | | D41858P | 27 | | | ALL |
| 0069 | 22 | GA | | | 35-0 | 26-16-11 | TB0112A | C017 | 2 | | D41858P | 28 | | | 001-099 |
| 0069 | 22 | GA | | | 34-0 | 26-16-11 | D40808J | 10 | | | D41858P | 28 | | | 115-199 |
| 0070Y | 20 | QB | | | 24-0 | 27-41-11 | D40808J | 22 | | | TB0100X | B003 | BJ | | ALL |
| 0075 | 22 | GA | | | 35-0 | 26-15-11 | D40808J | 12 | | | D41060P | 38 | | | ALL |
| 0078 | 24 | GK | | | 40-0 | 21-58-12 | TB0115Y | A005 | BJ | | D41060P | 6 | | | ALL |
| 0079 | 24 | GK | | | 7-0 | 21-58-12 | D03518 | 18 | | | GD00608 | DC.. | 2 | | ALL |
| 0081 | 22 | GA | | | 22-0 | 76-11-11 | D41904P | 1 | | | TB0059X | B004 | BJ | | 001-099 |
| 0081 | 22 | GA | | | 21-0 | 76-11-11 | D41904P | 1 | | | TB0059X | B004 | BJ | | 115-199 |
| 0082 | 20 | GA | | | 7-0 | 26-21-11 | D41904P | 2 | | | D44108J | 2 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2150

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2156 | 286N2156 | | | FLIGHT DECK TO E/E BAY CAT "S2B" SYSTEM (continued) | | | | | | | | | | | |
| 0082 | 20 | | GA | | 6-0 | 26-21-11 | D41904P | | 2 | | D44108J | | 2 | | 115-199 |
| 0083 | 20 | | GA | | 7-0 | 26-21-11 | D41904P | | 3 | | D44106J | | 2 | | 001-099 |
| 0083 | 20 | | GA | | 6-0 | 26-21-11 | D41904P | | 3 | | D44106J | | 2 | | 115-199 |
| 0085 | 22 | | GA | | 8-0 | 33-16-52 | D03530 | | 4 | | TB0116Z | 10 | BJ | | ALL |
| 0089 | 22 | | GA | | 8-0 | 33-16-62 | D03530 | | 3 | | TB0116Y | A001 | BJ | | ALL |
| 0090 | 22 | | GA | | 10-0 | 30-21-11 | D03530 | | 8 | | D40808J | | 5 | | ALL |
| 0091 | 22 | | GA | | 38-0 | 30-21-11 | D03530 | | 7 | | D41858P | | 3 | | ALL |
| 0092 | 22 | | GA | | 38-0 | 30-21-11 | D03530 | | 11 | | D41858P | | 2 | | ALL |
| 0096 | 20 | | GA | | 7-0 | 33-13-31 | D03530 | | 1 | | TB0114Z | 11 | BJ | | ALL |
| 0097 | 20 | | GA | | 7-0 | 33-13-31 | D03530 | | 2 | | TB0114Z | 12 | BJ | | ALL |
| 0111 | 20 | | GA | | 7-0 | 33-13-31 | D03518 | | 1 | | TB0114Z | 11 | BJ | | ALL |
| 0112 | 20 | | GA | | 7-0 | 33-13-31 | D03518 | | 2 | | TB0114Z | 12 | BJ | | ALL |
| 0113 | 20 | | GA | | 8-0 | 26-21-11 | D03736 | | 5 | | GD00619 | DC.. | 2 | | ALL |
| 0114 | 20 | | GA | | 7-0 | 26-21-11 | D03736 | | 4 | | D41904P | | 5 | | 001-099 |
| 0114 | 20 | | GA | | 8-0 | 26-21-11 | D03736 | | 4 | | D41904P | | 5 | | 115-199 |
| 0115 | 20 | | GA | | 8-0 | 26-21-11 | D03736 | | 3 | | D41904P | | 6 | | ALL |
| 0116 | 20 | | GA | | 4-0 | 26-21-11 | D03736 | | 8 | | D44106J | | 5 | | ALL |
| 0117 | 20 | | GA | | 4-0 | 26-21-11 | D03736 | | 9 | | D44106J | | 1 | | ALL |
| 0118 | 20 | | GA | | 8-0 | 26-22-21 | D03736 | | 12 | | TB0121Y | C024 | BJ | | 001-099 |
| 0118 | 20 | | GA | | 33-0 | 26-22-21 | D03736 | | 12 | | D41060P | | 12 | | 115-199 |
| 0119 | 20 | | GA | | 8-0 | 26-22-21 | D03736 | | 7 | | D41904P | | 15 | | 001-099 |
| 0119 | 20 | | GA | | 33-0 | 26-22-21 | D03736 | | 7 | | D41060P | | 13 | | 115-199 |
| 0120 | 20 | | GA | | 4-0 | 26-23-11 | D41904P | | 7 | | SM00011 | | 9 | | 001-099 |
| 0120 | 20 | | GA | | 3-0 | 26-23-11 | D41904P | | 7 | | SM00011 | | 9 | | 115-199 |
| 0121 | 20 | | GA | | 7-0 | 26-23-11 | D03736 | | 6 | | SM00011 | | 9 | | ALL |
| 0122 | 22 | | GA | | 4-0 | 26-23-11 | D03736 | | 11 | | D44106J | | 4 | | 001-099 |
| 0122 | 20 | | GA | | 4-0 | 26-23-11 | D03736 | | 11 | | D44106J | | 4 | | 115-199 |
| 0123 | 22 | | GA | | 4-0 | 26-23-11 | D03736 | | 10 | | D44108J | | 3 | | 001-099 |
| 0123 | 20 | | GA | | 4-0 | 26-23-11 | D03736 | | 10 | | D44108J | | 3 | | 115-199 |
| 0124 | 24 | | GK | | 41-0 | 21-25-11 | D41060P | | 20 | | TB0059X | B010 | BJ | | 001-099 |
| 0124 | 24 | | GK | | 39-0 | 21-25-11 | D41060P | | 20 | | TB0059X | B010 | BJ | | 115-199 |
| 0125 | 22 | | GA | | 26-0 | SPARE | D41060P | | 10 | | D41858P | | 1 | | 001-002 |
| 0125 | 22 | | GA | | 19-0 | SPARE | D41060P | | 10 | | D41858P | | 1 | | 003-099, 115-199 |
| 0127 | 22 | | GA | | 21-0 | SPARE | D41060P | | 14 | | D41858P | | 5 | | 001-002 |
| 0127 | 22 | | GA | | 19-0 | SPARE | D41060P | | 14 | | D41858P | | 5 | | 003-099, 115-199 |
| 0130 | 20 | | GA | | 35-0 | SPARE | D41060P | | 17 | | D40808J | | 29 | | 001-099 |
| 0131 | 20 | | GA | | 35-0 | SPARE | D41060P | | 19 | | D40808J | CAP | Y | | 001-002 |
| 0131 | 20 | | GA | | 35-0 | SPARE | D41060P | | 19 | | D40808J | | 13 | | 003-099 |
| 0131 | 20 | | GA | | 19-0 | SPARE | D41060P | | 19 | | D41858P | CAP | Y | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2150

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2156 | 286N2156 | | | FLIGHT DECK TO E/E BAY CAT "S2B" SYSTEM (continued) | | | | | | | | | | | |
| 0132 | 16 | | GA | | 39-0 | SPARE | D41060P | 21 | | | D03530 | CAP | Y | | 115-199 |
| 0133 | 20 | | GA | | 19-0 | SPARE | D41060P | 22 | | | D41858P | 14 | | | 115-199 |
| 0134 | 20 | | GA | | 19-0 | SPARE | D41060P | 36 | | | D41858P | 15 | | | 115-199 |
| 0135 | 20 | | GA | | 34-0 | SPARE | D40808J | 32 | | | D41858P | 16 | | | 001-002 |
| 0135 | 20 | | GA | | 19-0 | SPARE | D41060P | 24 | | | D41858P | 16 | | | 115-199 |
| 0136 | 20 | | GA | | 34-0 | SPARE | D40808J | 25 | | | D41858P | 17 | | | 001-002 |
| 0136 | 20 | | GA | | 19-0 | SPARE | D41060P | 25 | | | D41858P | 17 | | | 115-199 |
| 0137 | 20 | | GA | | 19-0 | SPARE | D41060P | 26 | | | D41858P | 18 | | | 115-199 |
| 0138 | 20 | | GA | | 19-0 | SPARE | D41060P | 27 | | | D41858P | 19 | | | 115-199 |
| 0139 | 20 | | GA | | 19-0 | SPARE | D41060P | 28 | | | D41858P | 20 | | | 115-199 |
| 0140 | 20 | | GA | | 19-0 | SPARE | D41060P | 29 | | | D41858P | 21 | | | 115-199 |
| 0141 | 20 | | GA | | 38-0 | SPARE | D03530 | CAP | Y | | D41858P | 22 | | | 115-199 |
| 0143 | 20 | | GA | | 38-0 | SPARE | D03530 | CAP | Y | | D41858P | 24 | | | 115-199 |
| 0144 | 20 | | GA | | 38-0 | SPARE | D03530 | CAP | Y | | D41858P | 25 | | | ALL |
| 0145 | 20 | | GA | | 38-0 | 30-21-11 | D03530 | 12 | | | D41858P | 26 | | | ALL |
| 0146 | 20 | | GA | | 39-0 | SPARE | D03530 | CAP | Y | | D41060P | 30 | | | 115-199 |
| 0147 | 22 | | GA | | 39-0 | 21-58-12 | D03518 | 12 | | | D41060P | 31 | | | ALL |
| 0148 | 24 | | GK | | 39-0 | 21-58-12 | D03518 | 20 | | | D41060P | 32 | | | ALL |
| 0149 | 24 | | GK | | 39-0 | 21-58-12 | D03518 | 5 | | | D41060P | 34 | | | ALL |
| 0150 | 22 | | GA | | 39-0 | 21-58-12 | D03518 | 11 | | | D41060P | 35 | | | ALL |
| 0151 | 22 | | GA | | 11-0 | SPARE | D40808J | 13 | | | TB0115X | C016 | BJ | | 115-199 |
| 0152 | 22 | | GA | | 11-0 | SPARE | D40808J | 14 | | | TB0115X | C015 | BJ | | 115-199 |
| 0153 | 20 | | GA | | 11-0 | 28-22-31 | D40808J | 28 | | | TB0115X | A001 | BJ | | ALL |
| 0155 | 20 | | GA | | 6-0 | 33-11-61 | D03534 | 13 | | | GD00608 | AC.. | 2 | | ALL |
| 0156 | 24 | | GK | | 15-0 | 33-11-61 | D03534 | 12 | | | TB0121Y | A024 | BJ | | ALL |
| 0157 | 20 | | GA | | 5-0 | 33-11-61 | L00533 | = G | C | | GD00619 | AC.. | 2 | | 001-099 |
| 0159 | 24 | | GK | | 8-0 | 33-11-61 | D03534 | 11 | | | TB0116X | B018 | BJ | | ALL |
| 0160 | 24 | | GK | | 38-0 | 21-58-13 | D03518 | 17 | | | D41858P | 4 | | | ALL |
| 0168 | 22 | | GA | | 9-0 | 23-51-11 | D40808J | 8 | | | TB0113A | A007 | 2 | | 001-099 |
| 0169 | 22 | | GA | | 9-0 | 23-51-11 | D40808J | 23 | | | TB0113A | A008 | 2 | | 001-099 |
| 0170 | 22 | | GA | | 2-0 | 23-51-11 | TB0113A | C007 | 2 | | TB0113A | C008 | 2 | | 001-099 |
| 0171 | 24 | | GK | | 7-0 | 26-16-11 | D40808J | 10 | | | TB0112A | A018 | 2 | | 001-099 |
| 0172 | 24 | | GK | | 2-0 | 26-16-11 | TB0112A | C018 | 2 | | TB0112A | C017 | 2 | | 001-099 |
| 0173 | 22 | | GA | | 39-0 | 21-58-15 | D41060P | 9 | | | D03518 | 9 | | | 001-099 |
| 0173 | 22 | | GA | | 39-0 | 21-58-15 | D03518 | 9 | | | D41060P | 9 | | | 115-199 |
| 0174 | 22 | | GA | | 34-0 | 33-51-11 | D40808J | 26 | | | D41858P | 6 | | | ALL |
| 0175 | 22 | | GA | | 34-0 | 33-51-11 | D40808J | 27 | | | D41858P | 7 | | | ALL |
| 0176 | 22 | | GA | | 26-0 | 78-34-21 | D40808J | 30 | | | TB0158Y | A002 | BJ | | 001-002 |
| 0176 | 22 | | GA | | 26-0 | SPARE | D40808J | 30 | | | TB0058Y | CAP | Y | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2150

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2156 | 286N2156 | | | | FLIGHT DECK TO E/E BAY CAT "S2B" SYSTEM (continued) | | | | | | | | | | | | |
| 0177 | 22 | | GA | | 7-0 | 21-58-12 | D03518 | 10 | | | | GD00608 | DC.. | 2 | | ALL | |
| 0178 | 22 | | GA | | 9-0 | 21-58-12 | TB0115Y | A005 | BJ | | | D03518 | 13 | | | ALL | |
| 0179 | 20 | | GA | | 7-0 | 21-58-13 | D03518 | 15 | | | | GD00608 | AC.. | 2 | | ALL | |
| 0180 | 20 | | GA | | 9-0 | 21-58-13 | TB0115X | C019 | BJ | | | D03518 | 14 | | | ALL | |
| 0191 | 24 | | GK | | 7-0 | 28-25-11 | D40808J | 1 | | | | TB0112X | D004 | BJ | | 001-099 | |
| 0191 | 22 | | GA | | 7-0 | 28-25-11 | D40808J | 1 | | | | TB0112X | D004 | BJ | | 115-199 | |
| 0192 | 24 | | GK | | 7-0 | 28-25-11 | D40808J | 2 | | | | TB0112X | C004 | BJ | | 001-099 | |
| 0192 | 22 | | GA | | 7-0 | 28-25-11 | D40808J | 2 | | | | TB0112X | C004 | BJ | | 115-199 | |
| 0193 | 22 | | GA | | 11-0 | 29-21-31 | D41904P | 13 | | | | TB0116Y | C006 | BJ | | 001-099 | |
| 0194 | 20 | | GA | | 8-0 | 24-33-12 | D40808J | 21 | | | | GD00596 | DC.. | 2 | | 001-099 | |
| 0195 | 22 | | GA | | 10-0 | 24-33-12 | D40808J | 15 | | | | D41904P | 10 | | | 001-099 | |
| 0196 | 22 | | GA | | 10-0 | 24-33-12 | D40808J | 17 | | | | D41904P | 11 | | | 001-099 | |
| 0197 | 22 | | GA | | 10-0 | 24-33-12 | D40808J | 18 | | | | D41904P | 12 | | | 001-099 | |
| 0198 | 22 | | GA | | 10-0 | 24-33-12 | D40808J | 11 | | | | D41904P | 9 | | | 001-099 | |
| 0236 | 20 | | GA | | 4-0 | 26-23-11 | SM00011 | | 9 | | | D44106J | 3 | | | 001-099 | |
| 0236 | 20 | | GA | | 5-0 | 26-23-11 | SM00011 | | 9 | | | D44106J | 3 | | | 115-199 | |
| 0250 | 22 | | GA | | 34-0 | 78-34-21 | D40808J | 31 | | | | D41858P | 11 | | | 003-099 | |
| 0251 | 20 | | GA | | 11-0 | 28-22-31 | D40808J | 34 | | | | TB0115X | B001 | BJ | | 009-099 | |
| 0252 | 22 | | GA | | 34-0 | 78-34-21 | D40808J | 34 | | | | D41858P | 13 | | | 001-002, 115-199 | |
| 0800 | 24 | | GK | | 9-0 | 21-33-12 | D03518 | 21 | | | | TB0115Y | A006 | BJ | | ALL | |
| 2001B | 24 | | GL | AA | 35-0 | 21-33-11 | D02698 | 7 | | | | D02694 | 2 | | | ALL | |
| 2001R | 24 | | GL | AA | 0-0 | 21-33-11 | D02698 | 6 | | | | D02694 | 1 | | | ALL | |
| 2002B | 24 | | GL | AB | 35-0 | 21-33-11 | D02698 | 9 | | | | D02694 | 4 | | | ALL | |
| 2002R | 24 | | GL | AB | 0-0 | 21-33-11 | D02698 | 8 | | | | D02694 | 3 | | | ALL | |
| 2501B | 24 | | G2 | BB | 23-0 | 23-51-41 | TB0158X | D004 | BJ | | | SP02156 | | 9 | | 001-099 | |
| 2501R | 24 | | G2 | BB | 0-0 | 23-51-41 | TB0158X | C004 | BJ | | | SP02158 | | 9 | | 001-099 | |
| 2501Z | | | | BB | 0-0 | 23-51-41 | TB0158X | A004 | BJ | | | SP02156 | DED | | | 001-099 | |
| A-BK | | | | | 0-0 | 23-51-41 | D00551 | | BLK | | | SP02158 | | 9 | | 001-099 | |
| A-BL | | | | | 0-0 | 23-51-41 | D00551 | | BLU | | | SP02156 | | 9 | | 001-099 | |
| A-WT | | | | | 0-0 | 33-11-61 | L00533 | | =P | | | TB0121Y | A024 | BJ | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2150

Page 8 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | Term | Type | Splice | To | | | Effectivity |
|------------------------|-------------|----|----|-----|---|----------|---------|-------|------|------|------|------|---------|--------|----|--|-------------|
| | GA | CO | TY | | FT-IN | Equip | | Equip | Term | Type | | | | Splice | | | |
| W2193 | 286N2193 | | | | AURAL WARNING , CAPT LOUDSPEAKER TO P51 | | | | | | | | | | | | |
| 0001 | 22 | GA | | | 6-0 | 31-51-11 | D00109 | | 4 | | | | TB0115X | C001 | BJ | | 001-099 |
| 0001 | 22 | GA | | | 5-0 | 31-51-11 | D00109 | | 4 | | | | TB0115X | C001 | BJ | | 115-199 |
| 0004 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 6 | | | | D40587P | 4 | | | ALL |
| 0005 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 4 | | | | D40587P | 5 | | | ALL |
| 0006 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 3 | | | | D40587P | 6 | | | ALL |
| 0007 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 2 | | | | D40587P | 7 | | | ALL |
| 0008 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 7 | | | | D40587P | 8 | | | ALL |
| 0009 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 8 | | | | D40587P | 9 | | | ALL |
| 0010 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 9 | | | | D40587P | 10 | | | ALL |
| 0011 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 5 | | | | D40587P | 11 | | | ALL |
| 0012 | 24 | GK | | | 3-0 | 27-32-12 | D00153 | | 24 | | | | D40587P | 12 | | | ALL |
| 0013 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 16 | | | | D40587P | 13 | | | ALL |
| 0014 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 14 | | | | D40587P | 14 | | | ALL |
| 0015 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 13 | | | | D40587P | 15 | | | ALL |
| 0016 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 12 | | | | D40587P | 16 | | | ALL |
| 0017 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 17 | | | | D40587P | 17 | | | ALL |
| 0018 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 18 | | | | D40587P | 18 | | | ALL |
| 0019 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 19 | | | | D40587P | 19 | | | ALL |
| 0020 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 15 | | | | D40587P | 20 | | | ALL |
| 0021 | 24 | GK | | | 3-0 | 27-32-22 | D00153 | | 34 | | | | D40587P | 21 | | | ALL |
| 0022 | 22 | GA | | | 3-0 | 31-51-11 | D00153 | | 25 | | | | D40587P | 22 | | | ALL |
| 0023 | 22 | GA | | | 3-0 | 31-51-11 | D00153 | | 26 | | | | D40587P | 23 | | | ALL |
| 0024 | 22 | GA | | | 3-0 | 31-51-11 | D00153 | | 27 | | | | D40587P | 24 | | | ALL |
| 0025 | 22 | GA | | | 3-0 | 31-51-12 | D00153 | | 35 | | | | D40587P | 25 | | | ALL |
| 0026 | 22 | GA | | | 3-0 | 31-51-12 | D00153 | | 36 | | | | D40587P | 26 | | | ALL |
| 0027 | 22 | GA | | | 3-0 | 31-51-12 | D00153 | | 37 | | | | D40587P | 27 | | | ALL |
| 0028 | 22 | GA | | | 3-0 | 31-51-12 | D00153 | | 1 | | | | D40587P | 28 | | | ALL |
| 0029 | 22 | GA | | | 3-0 | 31-51-11 | D00153 | | 11 | | | | D40587P | 29 | | | ALL |
| 3501B | 24 | G3 | AB | | 43-0 | 31-51-31 | D00109 | | 5 | | | | D40587P | 2 | | | ALL |
| 3501R | 24 | G3 | AB | | 0-0 | 31-51-31 | D00109 | | 3 | | | | D40587P | 1 | | | ALL |
| 3501Y | 24 | G3 | AB | | 0-0 | 31-51-31 | D00109 | | 6 | | | | D40587P | 3 | | | ALL |
| 3501Z | | | AB | | 0-0 | 31-51-31 | D00109 | DED | | | | | D40587P | 31 | | | ALL |
| W2195 | 286N2195 | | | | AURAL WARNING , F/O LOUDSPEAKER TO P51 | | | | | | | | | | | | |
| 0001 | 22 | GA | | | 8-0 | 31-51-12 | D00111 | | 4 | | | | TB0113X | C011 | BJ | | 001-099 |
| 0001 | 22 | GA | | | 9-0 | 31-51-12 | D00111 | | 4 | | | | TB0113X | C011 | BJ | | 115-199 |
| 3501B | 24 | G3 | AB | | 28-0 | 31-51-32 | D00111 | | 5 | | | | D40585P | 2 | | | ALL |
| 3501R | 24 | G3 | AB | | 0-0 | 31-51-32 | D00111 | | 3 | | | | D40585P | 1 | | | ALL |
| 3501Y | 24 | G3 | AB | | 0-0 | 31-51-32 | D00111 | | 6 | | | | D40585P | 3 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2190

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2195 | 286N2195 | | | AURAL WARNING , F/O LOUDSPEAKER TO P51 (continued) | | | | | | | | | | | |
| 3501Z | | | | AB | 0-0 | 31-51-32 | D00111 | DED | | | D40585P | 4 | | | ALL |

WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details

91-21-11
Section W2190
Page 2 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2221 | 286N2221 | | | M00059 (P-5 PNL) TO E2-4 - LEFT | | | | | | | | | | | |
| 0001 | 24 | | GK | | 34-0 | 34-21-11 | D00147 | | 13 | | D42201P | | 1 | | 001-099 |
| 0001 | 24 | | GK | | 36-0 | 34-21-11 | D00147 | | 13 | | D42201P | | 1 | | 115-199 |
| 0002 | 24 | | GK | | 34-0 | 34-21-11 | D00147 | | 12 | | D42201P | | 2 | | 001-099 |
| 0002 | 24 | | GK | | 36-0 | 34-21-11 | D00147 | | 12 | | D42201P | | 2 | | 115-199 |
| 0003 | 22 | | GA | | 34-0 | 34-21-11 | D00147 | | 14 | | D42201P | | 3 | | 001-099 |
| 0003 | 22 | | GA | | 36-0 | 34-21-11 | D00147 | | 14 | | D42201P | | 3 | | 115-199 |
| 0004 | 22 | | GA | | 34-0 | 34-21-11 | D00147 | | 15 | | D42201P | | 4 | | 001-099 |
| 0004 | 22 | | GA | | 36-0 | 34-21-11 | D00147 | | 15 | | D42201P | | 4 | | 115-199 |
| 0005 | 22 | | GA | | 34-0 | 34-21-11 | D00147 | | 16 | | D42201P | | 5 | | 001-099 |
| 0005 | 22 | | GA | | 36-0 | 34-21-11 | D00147 | | 16 | | D42201P | | 5 | | 115-199 |
| 0006 | 22 | | GA | | 34-0 | 34-21-11 | D00147 | | 17 | | D42201P | | 6 | | 001-099 |
| 0006 | 22 | | GA | | 36-0 | 34-21-11 | D00147 | | 17 | | D42201P | | 6 | | 115-199 |
| 0007 | 20 | | GA | | 34-0 | 34-21-11 | D00147 | | 3 | | D42201P | | 7 | | 001-099 |
| 0007 | 20 | | GA | | 36-0 | 34-21-11 | D00147 | | 3 | | D42201P | | 7 | | 115-199 |
| 0008 | 20 | | GA | | 34-0 | 34-21-11 | D00147 | | 4 | | D42201P | | 8 | | 001-099 |
| 0008 | 20 | | GA | | 36-0 | 34-21-11 | D00147 | | 4 | | D42201P | | 8 | | 115-199 |
| 0009 | 20 | | GA | | 34-0 | 34-21-11 | D00147 | | 5 | | D42201P | | 9 | | 001-099 |
| 0009 | 20 | | GA | | 36-0 | 34-21-11 | D00147 | | 5 | | D42201P | | 9 | | 115-199 |
| 0010 | 20 | | GA | | 5-0 | 34-21-11 | D00147 | | 8 | | GD00599 | ST.. | 2 | | 001-099 |
| 0010 | 20 | | GA | | 7-0 | 34-21-11 | D00147 | | 8 | | GD00599 | ST.. | 2 | | 115-199 |
| 0011 | 20 | | GA | | 6-0 | 33-13-31 | D00147 | | 2 | | TB0114Z | 10 | BJ | | 001-099 |
| 0011 | 20 | | GA | | 8-0 | 33-13-31 | D00147 | | 2 | | TB0114Z | 10 | BJ | | 115-199 |
| 0012 | 20 | | GA | | 6-0 | 33-13-31 | D00147 | | 1 | | TB0114Z | 8 | BJ | | 001-099 |
| 0012 | 20 | | GA | | 8-0 | 33-13-31 | D00147 | | 1 | | TB0114Z | 8 | BJ | | 115-199 |
| 0013 | 22 | | GA | | 37-0 | 33-16-21 | TB0112X | B016 | | BJ | D42201P | | 18 | | 001-099 |
| 0013 | 22 | | GA | | 38-0 | 33-16-21 | TB0112X | B016 | | BJ | D42201P | | 18 | | 115-199 |
| 0014 | 22 | | GA | | 8-0 | 33-16-12 | D00147 | | 18 | | TB0112X | A016 | BJ | | 001-099 |
| 0014 | 22 | | GA | | 9-0 | 33-16-12 | D00147 | | 18 | | TB0112X | A016 | BJ | | 115-199 |
| 0015 | 22 | | GA | | 8-0 | 33-16-12 | D00147 | | 10 | | TB0112Y | A002 | BJ | | 001-099 |
| 0015 | 22 | | GA | | 9-0 | 33-16-12 | D00147 | | 10 | | TB0112Y | A002 | BJ | | 115-199 |
| 0016 | 22 | | GA | | 8-0 | 33-16-12 | D00147 | | 11 | | TB0112Y | A002 | BJ | | 001-099 |
| 0016 | 22 | | GA | | 9-0 | 33-16-12 | D00147 | | 11 | | TB0112Y | A002 | BJ | | 115-199 |
| 0017 | 24 | | GK | | 8-0 | 21-58-11 | D00147 | | 19 | | TB0111Y | A009 | BJ | | ALL |
| 0018 | 24 | | GK | | 8-0 | 21-58-11 | D00147 | | 20 | | TB0111Y | C009 | BJ | | ALL |
| 0020 | 20 | | GA | | 8-0 | 21-58-11 | TB0111Y | C009 | | BJ | GD00599 | DC.. | 2 | | ALL |
| 5001B | 24 | | G2 | AA | 34-0 | 34-21-11 | D00147 | | 27 | | D42201P | | 11 | | 001-099 |
| 5001B | 24 | | G2 | AA | 36-0 | 34-21-11 | D00147 | | 27 | | D42201P | | 11 | | 115-199 |
| 5001R | 24 | | G2 | AA | 0-0 | 34-21-11 | D00147 | | 26 | | D42201P | | 10 | | ALL |
| 5001Z | | | | AA | 0-0 | 34-21-11 | GD00596 | | ST.. | 2 | D42201P | | 12 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2220

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2221 | 286N2221 | | | | M00059 (P-5 PNL) TO E2-4 - LEFT (continued) | | | | | | | | | | |
| 5002B | 24 | G2 | AB | | 34-0 | 34-21-11 | D00147 | 25 | | | D42201P | 15 | | | 001-099 |
| 5002B | 24 | G2 | AB | | 36-0 | 34-21-11 | D00147 | 25 | | | D42201P | 15 | | | 115-199 |
| 5002R | 24 | G2 | AB | | 0-0 | 34-21-11 | D00147 | 24 | | | D42201P | 14 | | | ALL |
| 5002Z | | | AB | | 0-0 | 34-21-11 | GD00596 | ST.. | 2 | | D42201P | 16 | | | ALL |
| W2223 | 286N2223 | | | | M59 (P-5 PNL) TO E2-4 - RIGHT | | | | | | | | | | |
| 0001 | 24 | GK | | | 37-0 | 34-21-21 | D00151 | 13 | | | D42203P | 1 | | | 001-099 |
| 0001 | 24 | GK | | | 38-0 | 34-21-21 | D00151 | 13 | | | D42203P | 1 | | | 115-199 |
| 0002 | 24 | GK | | | 37-0 | 34-21-21 | D00151 | 12 | | | D42203P | 2 | | | 001-099 |
| 0002 | 24 | GK | | | 38-0 | 34-21-21 | D00151 | 12 | | | D42203P | 2 | | | 115-199 |
| 0003 | 22 | GA | | | 37-0 | 34-21-21 | D00151 | 14 | | | D42203P | 3 | | | 001-099 |
| 0003 | 22 | GA | | | 38-0 | 34-21-21 | D00151 | 14 | | | D42203P | 3 | | | 115-199 |
| 0004 | 22 | GA | | | 37-0 | 34-21-21 | D00151 | 15 | | | D42203P | 4 | | | 001-099 |
| 0004 | 22 | GA | | | 38-0 | 34-21-21 | D00151 | 15 | | | D42203P | 4 | | | 115-199 |
| 0005 | 22 | GA | | | 37-0 | 34-21-21 | D00151 | 17 | | | D42203P | 5 | | | 001-099 |
| 0005 | 22 | GA | | | 38-0 | 34-21-21 | D00151 | 17 | | | D42203P | 5 | | | 115-199 |
| 0006 | 20 | GA | | | 38-0 | 34-21-21 | D00151 | 3 | | | D42203P | 6 | | | ALL |
| 0007 | 20 | GA | | | 38-0 | 34-21-21 | D00151 | 4 | | | D42203P | 7 | | | ALL |
| 0008 | 20 | GA | | | 38-0 | 34-21-21 | D00151 | 5 | | | D42203P | 8 | | | ALL |
| 0009 | 22 | GA | | | 38-0 | 34-21-21 | D00151 | 16 | | | D42203P | 9 | | | ALL |
| 0010 | 20 | GA | | | 5-0 | 34-21-21 | D00151 | 8 | | | GD00599 | ST.. | 2 | | 001-099 |
| 0010 | 20 | GA | | | 6-0 | 34-21-21 | D00151 | 8 | | | GD00599 | ST.. | 2 | | 115-199 |
| 0011 | 22 | GA | | | 5-0 | 33-16-32 | D00151 | 18 | | | TB0113X | B012 | BJ | | 001-099 |
| 0011 | 22 | GA | | | 7-0 | 33-16-32 | D00151 | 18 | | | TB0113X | B012 | BJ | | 115-199 |
| 0012 | 22 | GA | | | 8-0 | 33-16-62 | D00151 | 11 | | | TB0116Y | C005 | BJ | | 001-099 |
| 0012 | 22 | GA | | | 9-0 | 33-16-62 | D00151 | 11 | | | TB0116Y | C005 | BJ | | 115-199 |
| 0013 | 22 | GA | | | 8-0 | 33-16-62 | D00151 | 10 | | | TB0116Y | C005 | BJ | | 001-099 |
| 0013 | 22 | GA | | | 9-0 | 33-16-62 | D00151 | 10 | | | TB0116Y | C005 | BJ | | 115-199 |
| 0014 | 22 | GA | | | 39-0 | 33-16-31 | TB0113X | A012 | BJ | | D42203P | 20 | | | 001-099 |
| 0014 | 22 | GA | | | 38-0 | 33-16-31 | TB0113X | A012 | BJ | | D42203P | 20 | | | 115-199 |
| 0015 | 24 | GK | | | 6-0 | 21-58-11 | D00151 | 19 | | | TB0111Y | A009 | BJ | | 001-099 |
| 0015 | 24 | GK | | | 7-0 | 21-58-11 | D00151 | 19 | | | TB0111Y | A009 | BJ | | 115-199 |
| 0016 | 24 | GK | | | 6-0 | 21-58-11 | D00151 | 20 | | | TB0111Y | C009 | BJ | | 001-099 |
| 0016 | 24 | GK | | | 7-0 | 21-58-11 | D00151 | 20 | | | TB0111Y | C009 | BJ | | 115-199 |
| 5001B | 24 | G2 | AA | | 38-0 | 34-21-21 | D00151 | 27 | | | D42203P | 11 | | | ALL |
| 5001R | 24 | G2 | AA | | 0-0 | 34-21-21 | D00151 | 26 | | | D42203P | 10 | | | ALL |
| 5001Z | | | AA | | 0-0 | 34-21-21 | GD00596 | ST.. | 2 | | D42203P | 12 | | | ALL |
| 5002B | 24 | G2 | AB | | 38-0 | 34-21-21 | D00151 | 25 | | | D42203P | 14 | | | ALL |
| 5002R | 24 | G2 | AB | | 0-0 | 34-21-21 | D00151 | 24 | | | D42203P | 13 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2220

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2223 | 286N2223 | | | | M59 (P-5 PNL) TO E2-4 - RIGHT (continued) | | | | | | | | | | |
| 5002Z | | | | AB | 0-0 | 34-21-21 | GD00596 | ST.. | 2 | | D42203P | 15 | | | ALL |
| W2225 | 286N2225 | | | | M59 (P-5 PNL) TO E2-4 - CENTER | | | | | | | | | | |
| 0001 | 24 | | GK | | 35-0 | 34-21-31 | D00149 | | 13 | | D42205P | 1 | | | ALL |
| 0002 | 24 | | GK | | 35-0 | 34-21-31 | D00149 | | 12 | | D42205P | 2 | | | ALL |
| 0003 | 22 | | GA | | 35-0 | 34-21-31 | D00149 | | 14 | | D42205P | 3 | | | ALL |
| 0004 | 22 | | GA | | 35-0 | 34-21-31 | D00149 | | 15 | | D42205P | 4 | | | ALL |
| 0005 | 22 | | GA | | 35-0 | 34-21-31 | D00149 | | 16 | | D42205P | 5 | | | ALL |
| 0006 | 22 | | GA | | 35-0 | 34-21-31 | D00149 | | 17 | | D42205P | 6 | | | ALL |
| 0007 | 20 | | GA | | 35-0 | 34-21-31 | D00149 | | 3 | | D42205P | 7 | | | ALL |
| 0008 | 20 | | GA | | 35-0 | 34-21-31 | D00149 | | 4 | | D42205P | 8 | | | ALL |
| 0009 | 20 | | GA | | 35-0 | 34-21-31 | D00149 | | 5 | | D42205P | 9 | | | ALL |
| 0010 | 20 | | GA | | 5-0 | 34-21-31 | D00149 | | 8 | | GD00599 | ST.. | 2 | | 001-099 |
| 0010 | 20 | | GA | | 5-1 | 34-21-31 | D00149 | | 8 | | GD00599 | ST.. | 2 | | 115-199 |
| 0011 | 24 | | GK | | 6-0 | 21-58-11 | D00149 | | 19 | | TB0111Y | A009 | BJ | | 001-099 |
| 0011 | 24 | | GK | | 8-0 | 21-58-11 | D00149 | | 19 | | TB0111Y | A009 | BJ | | 115-199 |
| 0012 | 24 | | GK | | 6-0 | 21-58-11 | D00149 | | 20 | | TB0111Y | C009 | BJ | | 001-099 |
| 0012 | 24 | | GK | | 8-0 | 21-58-11 | D00149 | | 20 | | TB0111Y | C009 | BJ | | 115-199 |
| 0013 | 22 | | GA | | 38-0 | 33-16-61 | TB0116X | A011 | BJ | | D42205P | 16 | | | 001-099 |
| 0013 | 22 | | GA | | 39-0 | 33-16-61 | TB0116X | A011 | BJ | | D42205P | 16 | | | 115-199 |
| 0014 | 22 | | GA | | 9-0 | 33-16-62 | D00149 | | 18 | | TB0116X | B011 | BJ | | 001-099 |
| 0014 | 22 | | GA | | 7-0 | 33-16-62 | D00149 | | 18 | | TB0116X | B011 | BJ | | 115-199 |
| 0015 | 22 | | GA | | 7-0 | 33-16-32 | D00149 | | 11 | | TB0114Y | A003 | BJ | | ALL |
| 0016 | 22 | | GA | | 7-0 | 33-16-32 | D00149 | | 10 | | TB0114Y | A003 | BJ | | ALL |
| 5001B | 24 | | G2 | AA | 35-0 | 34-21-31 | D00149 | | 27 | | D42205P | 11 | | | ALL |
| 5001R | 24 | | G2 | AA | 0-0 | 34-21-31 | D00149 | | 26 | | D42205P | 10 | | | ALL |
| 5001Z | | | | AA | 0-0 | 34-21-31 | GD00600 | ST.. | 2 | | D42205P | 12 | | | ALL |
| 5002B | 24 | | G2 | AB | 35-0 | 34-21-31 | D00149 | | 25 | | D42205P | 14 | | | ALL |
| 5002R | 24 | | G2 | AB | 0-0 | 34-21-31 | D00149 | | 24 | | D42205P | 13 | | | ALL |
| 5002Z | | | | AB | 0-0 | 34-21-31 | GD00600 | ST.. | 2 | | D42205P | 15 | | | ALL |
| W2227 | 286N2227 | | | | DUAL ADF CONTROL, P8 TO E6-1 | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 34-57-11 | D00781 | | 7 | | GD00082 | ST.. | 2 | | ALL |
| 0002 | 20 | | GA | | 5-0 | 34-57-11 | D00781 | | 10 | | TB0059X | C009 | BJ | | 001-099 |
| 0003 | 22 | | GA | | 143-0 | 34-57-11 | D00781 | | 9 | | D42005P | 7 | | | 001-099 |
| 0004 | 20 | | GA | | 5-0 | 34-57-11 | D00781 | | 8 | | GD00082 | AC.. | 2 | | 001-099 |
| 0005 | 20 | | GA | | 5-0 | 33-13-52 | D00781 | | 1 | | TB0159Z | 11 | BJ | | ALL |
| 0006 | 20 | | GA | | 5-0 | 33-13-52 | D00781 | | 2 | | GD00082 | AC.. | 2 | | ALL |
| 0007 | 24 | | GK | | 5-0 | 34-22-83 | D00781 | | 19 | | TB0059X | D008 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2220

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | |
| W2227 | 286N2227 | | | | DUAL ADF CONTROL, P8 TO E6-1 (continued) | | | | | | | | | | | | | |
| 1002 | 20 | | GT | AD | 5-0 | 34-57-11 | D00781 | 10 | | | TB0059X | C009 | BJ | | 115-199 | | | |
| 1002Z | | | | AD | 0-0 | 34-57-11 | D00781 | DED | | | TB0059X | DED | | | 115-199 | | | |
| 1003 | 20 | | GT | AB | 158-0 | 34-57-11 | D00781 | 9 | | | D42005P | 7 | | | 115-199 | | | |
| 1003Z | | | | AB | 0-0 | 34-57-11 | D00781 | DED | | | D42005P | DED | | | 115-199 | | | |
| 1004 | 20 | | GT | AC | 5-0 | 34-57-11 | D00781 | 8 | | | GD00082 | AC.. | 2 | | 115-199 | | | |
| 1004Z | | | | AC | 0-0 | 34-57-11 | D00781 | DED | | | GD00082 | DED | | | 115-199 | | | |
| 5001B | 24 | | G2 | AA | 143-0 | 34-57-11 | D00781 | 13 | | | D42005P | 2 | | | 001-099 | | | |
| 5001B | 24 | | G2 | AA | 158-0 | 34-57-11 | D00781 | 13 | | | D42005P | 2 | | | 115-199 | | | |
| 5001R | 24 | | G2 | AA | 0-0 | 34-57-11 | D00781 | 12 | | | D42005P | 1 | | | ALL | | | |
| 5001Z | | | | AA | 0-0 | 34-57-11 | D00781 | 14 | | | D42005P | 3 | | | 001-099 | | | |
| 5001Z | | | | AA | 0-0 | 34-57-11 | D00781 | | | AA | D42005P | 3 | | | 115-199 | | | |
| 5002B | 24 | | G2 | AE | 158-0 | 34-57-11 | D00781 | 6 | | | D42005P | 5 | | | 115-199 | | | |
| 5002R | 24 | | G2 | AE | 0-0 | 34-57-11 | D00781 | 5 | | | D42005P | 4 | | | 115-199 | | | |
| 5002Z | | | | AE | 0-0 | 34-57-11 | D00781 | | | AA | D42005P | 6 | | | 115-199 | | | |
| FRAA | | | | | 0-0 | 34-57-11 | D00781 | | | AA | D00781 | 14 | | | 115-199 | | | |
| W2229 | 286N2229 | | | | DUAL ADF CONTROL, P8 TO E6-3 | | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 4-0 | 34-57-21 | D00441 | 7 | | | GD01650 | ST.. | 2 | | 001-009 | | | |
| 0001 | 20 | | GA | | 4-0 | 34-57-21 | D00783 | 7 | | | GD01650 | ST.. | 2 | | 010-099 | | | |
| 0001 | 20 | | GA | | 5-0 | 34-57-21 | D00783 | 7 | | | GD01650 | ST.. | 2 | | 115-199 | | | |
| 0005 | 20 | | GA | | 4-0 | 33-13-52 | D00441 | 1 | | | TB0159Z | 11 | BJ | | 001-009 | | | |
| 0006 | 20 | | GA | | 4-0 | 33-13-52 | D00441 | 2 | | | GD01650 | AC.. | 2 | * | 001-009 | | | |
| 0007 | 24 | | GK | | 5-0 | 34-22-93 | D00783 | 19 | | | TB0059X | C008 | BJ | | 115-199 | | | |
| 0014 | 24 | | GK | | 129-0 | SPARE | D41681P | 14 | | | D43683P | 14 | | | 001-009 | | | |
| 1002 | 22 | | GT | A | 4-0 | 34-57-21 | D00441 | 10 | | | TB0059X | D009 | BJ | | 001-009 | | | |
| 1002 | 20 | | GT | IA | 4-0 | 34-57-21 | D00783 | 10 | | | TB0059X | D009 | BJ | | 010-099 | | | |
| 1002 | 20 | | GT | IA | 5-0 | 34-57-21 | D00783 | 10 | | | TB0059X | D009 | BJ | | 115-199 | | | |
| 1002Z | | | | A | 0-0 | 34-57-21 | D00441 | DED | | | TB0059X | DED | | | 001-009 | | | |
| 1002Z | | | | IA | 0-0 | 34-57-21 | D00783 | DED | | | TB0059X | DED | | | 010-099, 115-199 | | | |
| 1003 | 22 | | GT | C | 146-0 | 34-57-21 | D00441 | 9 | | | D41681P | 7 | | | 001-009 | | | |
| 1003 | 20 | | GT | IB | 143-0 | 34-57-21 | D00783 | 9 | | | D41681P | 7 | | | 010-099 | | | |
| 1003 | 20 | | GT | IB | 164-0 | 34-57-21 | D00783 | 9 | | | D42007P | 7 | | | 115-199 | | | |
| 1003Z | | | | C | 0-0 | 34-57-21 | D00441 | DED | | | D41681P | DED | | | 001-009 | | | |
| 1003Z | | | | IB | 0-0 | 34-57-21 | D00783 | DED | | | D41681P | DED | | | 010-099 | | | |
| 1003Z | | | | IB | 0-0 | 34-57-21 | D00783 | DED | | | D42007P | DED | | | 115-199 | | | |
| 1004 | 20 | | GT | D | 4-0 | 34-57-21 | D00441 | 8 | | | GD01650 | AC.. | 2 | * | 001-009 | | | |
| 1004 | 20 | | GT | IC | 4-0 | 34-57-21 | D00783 | 8 | | | GD01650 | AC.. | 2 | | 010-099 | | | |
| 1004 | 20 | | GT | IC | 5-0 | 34-57-21 | D00783 | 8 | | | GD01650 | AC.. | 2 | | 115-199 | | | |
| 1004Z | | | | D | 0-0 | 34-57-21 | D00441 | DED | | | GD01650 | DED | | | 001-009 | | | |

WIRE LIST

D280N032

91-21-11

Section W2220

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----------|-------|-------------|--|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2229 | | 286N2229 | | | DUAL ADF CONTROL, P8 TO E6-3 (continued) | | | | | | | | | | |
| 1004Z | | | | IC | 0-0 | 34-57-21 | D00783 | DED | | | GD01650 | DED | | | 010-099, 115-199 |
| 2502B | | 24 | G2 | AC | 129-0 | SPARE | D41681P | 8 | | | D43683P | 9 | | | 001-009 |
| 2502R | | 24 | G2 | AC | 0-0 | SPARE | D41681P | 9 | | | D43683P | 8 | | | 001-009 |
| 2502Z | | | | AC | 0-0 | SPARE | D41681P | 10 | | | D43683P | 10 | | | 001-009 |
| 5001B | | 24 | G2 | AA | 146-0 | 34-57-21 | D00441 | 13 | | | D41681P | 2 | | | 001-009 |
| 5001B | | 24 | G2 | AA | 142-0 | 34-57-21 | D00783 | 13 | | | D41681P | 2 | | | 010-099 |
| 5001B | | 24 | G2 | AA | 164-0 | 34-57-21 | D00783 | 13 | | | D42007P | 2 | | | 115-199 |
| 5001R | | 24 | G2 | AA | 0-0 | 34-57-21 | D00441 | 12 | | | D41681P | 1 | | | 001-009 |
| 5001R | | 24 | G2 | AA | 0-0 | 34-57-21 | D00783 | 12 | | | D41681P | 1 | | | 010-099 |
| 5001R | | 24 | G2 | AA | 0-0 | 34-57-21 | D00783 | 12 | | | D42007P | 1 | | | 115-199 |
| 5001Z | | | | AA | 0-0 | 34-57-21 | D00441 | 14 | | | D41681P | 3 | | | 001-009 |
| 5001Z | | | | AA | 0-0 | 34-57-21 | D00783 | 14 | | | D41681P | 3 | | | 010-099 |
| 5001Z | | | | AA | 0-0 | 34-57-21 | D00783 | 14 | | | D42007P | 3 | | | 115-199 |
| 5006B | | 24 | G2 | AK | 129-0 | 34-22-91 | D41681P | 11 | | | D43683P | 11 | | | 001-002 |
| 5006B | | 24 | G2 | AK | 129-0 | SPARE | D41681P | 11 | | | D43683P | 11 | | | 003-009 |
| 5006R | | 24 | G2 | AK | 0-0 | 34-22-91 | D41681P | 12 | | | D43683P | 12 | | | 001-002 |
| 5006R | | 24 | G2 | AK | 0-0 | SPARE | D41681P | 12 | | | D43683P | 12 | | | 003-009 |
| 5006Z | | | | AK | 0-0 | 34-22-91 | D41681P | 13 | | | D43683P | 13 | | | 001-002 |
| 5006Z | | | | AK | 0-0 | SPARE | D41681P | 13 | | | D43683P | 13 | | | 003-009 |

WIRE LIST

D280N032

91-21-11

Section W2220

Page 5 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2230 | 286N2230 | | | | P6 TO E1-2 - T.R.U. LEFT DC OUTPUT | | | | | | | | | | |
| 0001 | 02 | | CQ | | 28-0 | 24-32-11 | T00101 | + | H | | TB5008 | = 1 | F | | ALL |
| 0002 | 02 | | CQ | | 3-7 | 24-32-11 | T00101 | - | G5 | | GD00530 | DC.. | H | | ALL |
| W2232 | 286N2232 | | | | P6 TO E1-1 - T.R.U. RIGHT DC OUTPUT | | | | | | | | | | |
| 0001 | 02 | | CQ | | 27-0 | 24-32-11 | T00102 | + | H | | TB5007 | = 1 | F | | 001-099 |
| 0001 | 02 | | CQ | | 27-1 | 24-32-11 | T00102 | + | H | | TB5007 | = 1 | F | | 115-199 |
| 0002 | 02 | | CQ | | 5-5 | 24-32-11 | T00102 | - | G5 | | GD00532 | DC.. | H | | 001-099 |
| 0002 | 02 | | CQ | | 5-11 | 24-32-11 | T00102 | - | G5 | | GD00532 | DC.. | H | | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W2230
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2240 | 286N2240 | | | P6 TO E/E AREA - LEFT BUSESSES | | | | | | | | | | | |
| 0001 | 16 | | GA | | 36-0 | 78-34-51 | D40284P | 5 | 16 | | SP01944 | | 9 | | 001-002, 115-199 |
| 0001 | 16 | | GA | | 39-0 | 78-34-51 | D40284P | 5 | 16 | | SP01944 | | 9 | | 003-099 |
| 0003 | 14 | | GA | | 34-0 | 24-32-11 | D40242P | 3 | | | D01776 | | 8 | | ALL |
| 0004 | 14 | | GA | | 34-0 | 24-32-11 | D40242P | 4 | | | D01776 | | 7 | | ALL |
| 0005 | 14 | | GA | | 34-0 | 24-32-11 | D40242P | 5 | | | D01776 | | 6 | | ALL |
| 0009 | 16 | | GA | | 4-0 | 24-32-11 | D01776 | 5 | | | GD02256 | ST.. | E | | ALL |
| 0601 | 22 | | GA | | 37-0 | SPARE | D41752P | 5 | | | D40284P | CAP | Y | | 001-002, 115-199 |
| 0602 | 22 | | GA | | 37-0 | SPARE | D41752P | 6 | | | D40284P | | 6 | | 115-199 |
| 0603 | 22 | | GA | | 37-0 | SPARE | D41752P | 7 | | | D40284P | | 7 | | 115-199 |
| 0604 | 22 | | GA | | 37-0 | SPARE | D41752P | 8 | | | D40284P | | 8 | | 115-199 |
| 0605 | 22 | | GA | | 37-0 | SPARE | D41752P | 9 | | | D40284P | | 9 | | 115-199 |
| 0606 | 20 | | GA | | 37-0 | SPARE | D40284P | 10 | | | D41752P | | 10 | | ALL |
| 0607 | 20 | | GA | | 37-0 | SPARE | D40284P | 11 | | | D41752P | | 11 | | 115-199 |
| 0608 | 20 | | GA | | 37-0 | SPARE | D40284P | 12 | | | D41752P | | 12 | | 115-199 |
| 0609 | 20 | | GA | | 37-0 | SPARE | D40284P | 13 | | | D41752P | | 13 | | 115-199 |
| 0610 | 16 | | GA | | 38-0 | 21-58-13 | D40242P | 6 | | | D40918P | | 6 | | ALL |
| 0611 | 16 | | GA | | 38-0 | 21-58-13 | D40242P | 7 | | | D40918P | | 7 | | ALL |
| 0612 | 16 | | GA | | 38-0 | 21-58-13 | D40242P | 8 | | | D40918P | | 8 | | ALL |
| 2002B | 22 | | GB | AA | 9-0 | 24-34-11 | D01776 | 4 | | | SP00604 | | 9 | | ALL |
| 2002R | 22 | | GB | AA | 0-0 | 24-34-11 | D01776 | 3 | | | SP00606 | | 9 | | ALL |
| 4001B | 24 | | GN | BA | 37-0 | 24-23-11 | D40284P | 3 | | | D41752P | | 3 | | ALL |
| 4001G | 24 | | GN | BA | 0-0 | 24-23-11 | D40284P | 4 | | | D41752P | | 4 | | ALL |
| 4001R | 24 | | GN | BA | 0-0 | 24-23-11 | D40284P | 1 | | | D41752P | | 1 | | ALL |
| 4001Y | 24 | | GN | BA | 0-0 | 24-23-11 | D40284P | 2 | | | D41752P | | 2 | | ALL |
| W2241 | 286N2241 | | | AP0001 TO E-E BAY - LEFT | | | | | | | | | | | |
| 0001 | 24 | | GK | | 25-0 | 34-12-12 | D40523J | 24 | | | D42011P | | 24 | | ALL |
| 0002 | 24 | | GK | | 28-0 | 34-21-11 | D40031J | 2 | | | D42015P | | 2 | | ALL |
| 0006 | 22 | | GA | | 25-0 | 22-14-11 | D40031J | 6 | | | D42011P | | 31 | | ALL |
| 0007 | 24 | | GK | | 36-0 | 34-13-21 | D40031J | 18 | | | D40639P | | 11 | | ALL |
| 0008 | 22 | | GA | | 28-0 | 22-34-11 | D40523J | 15 | | | D42021P | | 5 | | ALL |
| 0009 | 22 | | GA | | 28-0 | 22-41-13 | D40031J | 1 | | | D42021P | | 15 | | ALL |
| 0010 | 22 | | GA | | 28-0 | SPARE | D40039J | 6 | | | D42021P | | 6 | | 001-099 |
| 0010 | 22 | | GA | | 29-0 | SPARE | D40039J | 6 | | | D42021P | | 6 | | 115-199 |
| 0011 | 22 | | GA | | 25-0 | 22-41-13 | D40031J | 11 | | | D42011P | | 7 | | ALL |
| 0012 | 24 | | GK | | 28-0 | 34-46-11 | D40523J | 12 | | | D42021P | | 8 | | 001-099 |
| 0012 | 24 | | GK | | 28-0 | 34-46-11 | D40523J | 12 | | | D42021P | | 16 | | 115-199 |
| 0013 | 22 | | GA | | 25-0 | 34-61-15 | D40523J | 13 | | | D42011P | | 9 | | ALL |
| 0014 | 24 | | GK | | 25-0 | 34-22-17 | D40031J | 13 | | | D42011P | | 32 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2241 | 286N2241 | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | | |
| 0015 | 24 | | GK | | 25-0 | 34-22-17 | D40031J | | 15 | | D42011P | 34 | | | ALL |
| 0016 | 24 | | GK | | 25-0 | 34-22-17 | D40031J | | 16 | | D42011P | 35 | | | ALL |
| 0017 | 22 | | GA | | 28-0 | 34-46-11 | D40523J | | 17 | | D42021P | 9 | | | 001-099 |
| 0017 | 22 | | GA | | 28-0 | 34-46-11 | D40523J | | 17 | | D42021P | 17 | | | 115-199 |
| 0018 | 22 | | GA | | 28-0 | 34-46-11 | D40523J | | 18 | | D42021P | 10 | | | 001-099 |
| 0018 | 22 | | GA | | 28-0 | 34-46-11 | D40523J | | 18 | | D42021P | 18 | | | 115-199 |
| 0019 | 24 | | GK | | 25-0 | 34-22-17 | D40031J | | 19 | | D42011P | 33 | | | ALL |
| 0020 | 22 | | GA | | 31-0 | 34-22-17 | D40031J | | 20 | | D42019P | 1 | | | ALL |
| 0021 | 22 | | GA | | 31-0 | 34-12-61 | D40031J | | 21 | | D42019P | 13 | | | ALL |
| 0023 | 22 | | GA | | 25-0 | 34-22-16 | D40031J | | 10 | | D42011P | 8 | | | 001-099 |
| 0023 | 24 | | GK | | 25-0 | 34-22-16 | D40031J | | 10 | | D42011P | 8 | | | 115-199 |
| 0024 | 22 | | GA | | 25-0 | 32-42-11 | D40039J | | 34 | | D42011P | 36 | | | 001-099 |
| 0024 | 22 | | GA | | 26-0 | 32-42-11 | D40039J | | 34 | | D42011P | 36 | | | 115-199 |
| 0025 | 24 | | GK | | 36-0 | 31-51-42 | D40031J | | 14 | | D40639P | 14 | | | ALL |
| 0026 | 22 | | GA | | 36-0 | 34-16-11 | D40523J | | 26 | | D40639P | 10 | | | ALL |
| 0028 | 22 | | GA | | 28-0 | SPARE | D40523J | | 28 | | D42021P | 28 | | | 115-199 |
| 0029 | 22 | | GA | | 36-0 | 34-12-61 | D40523J | | 29 | | D42011P | 39 | | | 001-099 |
| 0029 | 22 | | GA | | 25-0 | 34-12-61 | D40523J | | 29 | | D42011P | 39 | | | 115-199 |
| 0030 | 22 | | GA | | 36-0 | 34-12-61 | D40523J | | 41 | | D42011P | 40 | | | 001-099 |
| 0030 | 22 | | GA | | 25-0 | 34-12-61 | D40523J | | 30 | | D42011P | 40 | | | 115-199 |
| 0031 | 24 | | GK | | 41-0 | SPARE | D40523J | | 31 | | D42023P | 20 | | | 001-099 |
| 0031 | 24 | | GK | | 40-0 | SPARE | D40523J | | 31 | | D42023P | 31 | | | 115-199 |
| 0032 | 22 | | GA | | 26-0 | SPARE | D40039J | | 35 | | D42011P | 37 | | | 115-199 |
| 0033 | 22 | | GA | | 25-0 | 34-61-15 | D40039J | | 36 | | D42011P | 38 | | | 001-099 |
| 0033 | 22 | | GA | | 26-0 | 34-61-15 | D40039J | | 36 | | D42011P | 38 | | | 115-199 |
| 0035 | 22 | | GA | | 31-0 | 31-31-31 | D40031J | | 3 | | D42019P | 10 | | | 115-199 |
| 0038 | 24 | | GK | | 28-0 | SPARE | D40523J | | 16 | | D42021P | 1 | | | 001-099 |
| 0038 | 22 | | GA | | 28-0 | SPARE | D40523J | | 16 | | D42021P | 1 | | | 115-199 |
| 0039 | 22 | | GA | | 28-0 | 34-46-11 | D40523J | | 19 | | D42021P | 4 | | | 001-099 |
| 0039 | 22 | | GA | | 28-0 | 34-46-11 | D40523J | | 19 | | D42021P | 27 | | | 115-199 |
| 0040 | 22 | | GA | | 28-0 | SPARE | D40523J | | 23 | | D42021P | 23 | | | 115-199 |
| 0041 | 22 | | GA | | 40-0 | SPARE | D40523J | | 25 | | D42023P | 13 | | | 115-199 |
| 0043 | 22 | | GA | | 36-0 | SPARE | D40523J | | 48 | | D40639P | 12 | | | 115-199 |
| 0044 | 22 | | GA | | 36-0 | 31-51-43 | D40523J | | 14 | | D40639P | 13 | | | ALL |
| 0045 | 22 | | GA | | 29-0 | SPARE | D40039J | | 7 | | D42021P | 7 | | | 115-199 |
| 0046 | 22 | | GA | | 28-0 | 34-22-16 | D40523J | | 11 | | D42013P | 27 | | | 001-099 |
| 0046 | 22 | | GA | | 27-0 | 34-22-16 | D40523J | | 11 | | D42013P | 36 | | | 115-199 |
| 0047 | 22 | | GA | | 31-0 | 34-32-11 | D40031J | | 47 | | D43009P | 6 | | | 001-099 |
| 0047 | 22 | | GA | | 153-0 | 34-32-11 | D40031J | | 47 | | D42001P | 11 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2241 | 286N2241 | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | | |
| 0048 | 22 | | GA | | 31-0 | 34-32-11 | D40031J | | 48 | | D43009P | | 7 | | 001-099 |
| 0048 | 22 | | GA | | 153-0 | 34-32-11 | D40031J | | 48 | | D42001P | | 12 | | 115-199 |
| 0049 | 22 | | GA | | 31-0 | 34-32-11 | D40031J | | 49 | | D43009P | | 8 | | 001-099 |
| 0049 | 22 | | GA | | 153-0 | 34-32-11 | D40031J | | 49 | | D42001P | | 13 | | 115-199 |
| 0050 | 22 | | GA | | 36-0 | 34-16-11 | D40523J | | 10 | | D40639P | | 6 | | ALL |
| 0051 | 22 | | GA | | 31-0 | 34-12-61 | D40031J | | 12 | | D42019P | | 5 | | ALL |
| 0052 | 22 | | GA | | 36-0 | SPARE | D40039J | | 9 | | D40639P | | 2 | | 115-199 |
| 0053 | 22 | | GA | | 36-0 | SPARE | D40039J | | 27 | | D40639P | | 3 | | 115-199 |
| 0054 | 22 | | GA | | 36-0 | 31-51-21 | D40039J | | 31 | | D40639P | | 4 | | ALL |
| 0055 | 22 | | GA | | 36-0 | 31-51-21 | D40039J | | 32 | | D40639P | | 5 | | ALL |
| 0057 | 24 | | GK | | 25-0 | 34-22-17 | D40031J | | 17 | | D42011P | | 15 | | ALL |
| 0058 | 22 | | GA | | 28-0 | 22-11-12 | D40629J | | 1 | | D42013P | | 1 | | ALL |
| 0059 | 22 | | GA | | 28-0 | SPARE | D40629J | | 2 | | D42013P | | 2 | | 001-099 |
| 0059 | 22 | | GA | | 28-0 | 22-11-12 | D40629J | | 2 | | D42013P | | 2 | | 115-199 |
| 0060 | 22 | | GA | | 28-0 | 22-11-12 | D40629J | | 3 | | D42013P | | 3 | | ALL |
| 0061 | 22 | | GA | | 28-0 | 22-11-12 | D40629J | | 4 | | D42013P | | 4 | | ALL |
| 0062 | 22 | | GA | | 31-0 | 34-55-11 | D40629J | | 14 | | D42019P | | 14 | | ALL |
| 0063 | 22 | | GA | | 28-0 | 34-51-11 | D40629J | | 23 | | D42013P | | 14 | | ALL |
| 0064 | 22 | | GA | | 28-0 | SPARE | D40629J | | 27 | | D42013P | | 22 | | 115-199 |
| 0065 | 22 | | GA | | 28-0 | SPARE | D40629J | | 28 | | D42013P | | 23 | | 115-199 |
| 0066 | 22 | | GA | | 31-0 | SPARE | D40629J | | 35 | | D42019P | | 9 | | ALL |
| 0068 | 24 | | GK | | 28-0 | 22-32-15 | D40629J | | 47 | | D42021P | | 2 | | ALL |
| 0069 | 24 | | GK | | 28-0 | 22-32-15 | D40629J | | 48 | | D42021P | | 3 | | ALL |
| 0070 | 22 | | GA | | 41-0 | 26-11-11 | D40523J | | 53 | | D42023P | | 14 | | 001-099 |
| 0070 | 22 | | GA | | 40-0 | 26-11-11 | D40523J | | 53 | | D42023P | | 14 | | 115-199 |
| 0074 | 22 | | GA | | 41-0 | 79-33-11 | D40523J | | 54 | | D42023P | | 18 | | 001-099 |
| 0074 | 22 | | GA | | 40-0 | 79-33-11 | D40523J | | 54 | | D42023P | | 18 | | 115-199 |
| 0075 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 47 | | D40219P | | 1 | | 001-099 |
| 0075 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 47 | | D41833P | | 1 | | 115-199 |
| 0076 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 52 | | D40219P | | 2 | | 001-099 |
| 0076 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 52 | | D41833P | | 2 | | 115-199 |
| 0077 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 49 | | D40219P | | 3 | | 001-099 |
| 0077 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 49 | | D41833P | | 3 | | 115-199 |
| 0078 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 50 | | D40219P | | 4 | | 001-099 |
| 0078 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 50 | | D41833P | | 4 | | 115-199 |
| 0079 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 51 | | D40219P | | 5 | | 001-099 |
| 0079 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 51 | | D41833P | | 5 | | 115-199 |
| 0080 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 35 | | D40219P | | 6 | | 001-099 |
| 0080 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 35 | | D41833P | | 6 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2241 | 286N2241 | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | | |
| 0081 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 33 | | D40219P | | 7 | | 001-099 |
| 0081 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 33 | | D41833P | | 7 | | 115-199 |
| 0082 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 34 | | D40219P | | 8 | | 001-099 |
| 0082 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 34 | | D41833P | | 8 | | 115-199 |
| 0083 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 55 | | D40219P | | 9 | | 001-099 |
| 0083 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 55 | | D41833P | | 9 | | 115-199 |
| 0084 | 22 | | GA | | 31-0 | 31-31-31 | D40031J | | 38 | | D42019P | | 12 | | 115-199 |
| 0085 | 22 | | GA | | 31-0 | 31-31-31 | D40031J | | 39 | | D42019P | | 24 | | 115-199 |
| 0086 | 22 | | GA | | 31-0 | 31-31-31 | D40031J | | 40 | | D42019P | | 25 | | 115-199 |
| 0087 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 32 | | D40219P | | 10 | | 001-099 |
| 0087 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 32 | | D41833P | | 10 | | 115-199 |
| 0088 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 37 | | D40219P | | 13 | | 001-099 |
| 0088 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 37 | | D41833P | | 13 | | 115-199 |
| 0089 | 22 | | GA | | 31-0 | 31-31-31 | D40031J | | 4 | | D42019P | | 11 | | 115-199 |
| 0090 | 22 | | GA | | 28-0 | SPARE | D40523J | | 36 | | D42015P | | 3 | | 115-199 |
| 0091 | 22 | | GA | | 28-0 | 34-12-12 | D40629J | | 52 | | D42013P | | 31 | | 115-199 |
| 0092 | 22 | | GA | | 28-0 | 34-12-12 | D40629J | | 53 | | D42013P | | 32 | | 115-199 |
| 0093 | 22 | | GA | | 31-0 | 34-55-11 | D40039J | | 50 | | D42019P | | 22 | | 115-199 |
| 0094 | 24 | | GK | | 31-0 | 34-55-11 | D40039J | | 54 | | D42019P | | 26 | | 115-199 |
| 0096 | 24 | | GK | | 31-0 | 31-31-31 | D40039J | | 1 | | D42019P | | 4 | | 115-199 |
| 0097 | 24 | | GK | | 31-0 | 31-31-31 | D40039J | | 2 | | D42019P | | 2 | | 115-199 |
| 0098 | 24 | | GK | | 31-0 | 31-31-31 | D40039J | | 15 | | D42019P | | 3 | | 115-199 |
| 0099 | 22 | | GA | | 31-0 | SPARE | D40629J | | 36 | | D42019P | | 23 | | 115-199 |
| 0101 | 22 | | GA | | 31-0 | 31-31-31 | D40031J | | 5 | | D42019P | | 30 | | 115-199 |
| 0102 | 22 | | GA | | 31-0 | 31-31-31 | D40031J | | 31 | | D42019P | | 31 | | 115-199 |
| 0103 | 22 | | GA | | 29-0 | 22-14-11 | D40039J | | 3 | | D42013P | | 24 | | 001-099 |
| 0103 | 22 | | GA | | 28-0 | 22-14-11 | D40039J | | 3 | | D42013P | | 33 | | 115-199 |
| 0104 | 22 | | GA | | 29-0 | 22-14-11 | D40039J | | 4 | | D42013P | | 25 | | 001-099 |
| 0104 | 22 | | GA | | 28-0 | 22-14-11 | D40039J | | 4 | | D42013P | | 34 | | 115-199 |
| 0105 | 22 | | GA | | 29-0 | 22-14-11 | D40039J | | 5 | | D42013P | | 26 | | 001-099 |
| 0105 | 22 | | GA | | 28-0 | 22-14-11 | D40039J | | 5 | | D42013P | | 35 | | 115-199 |
| 0106 | 24 | | GK | | 42-0 | 34-22-37 | D40039J | | 33 | | D42023P | | 19 | | 001-099 |
| 0106 | 24 | | GK | | 41-0 | 34-22-37 | D40039J | | 33 | | D42023P | | 19 | | 115-199 |
| 0108 | 24 | | GK | | 32-0 | 31-31-61 | D40039J | | 17 | | D42019P | | 31 | | 001-099 |
| 0109 | 24 | | GK | | 32-0 | 31-31-61 | D40039J | | 18 | | D42019P | | 27 | | 001-099 |
| 0112 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 42 | | D40219P | | 11 | | 001-099 |
| 0112 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 42 | | D41833P | | 11 | | 115-199 |
| 0113 | 22 | | GA | | 44-0 | 32-42-12 | D40523J | | 43 | | D40219P | | 12 | | 001-099 |
| 0113 | 22 | | GA | | 157-0 | 32-42-12 | D40523J | | 43 | | D41833P | | 12 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2241 | 286N2241 | | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | | | |
| 0114 | 24 | | PK | | 34-0 | 34-61-16 | D40039J | | 8 | | | D42013P | 53 | | 115-199 | | |
| 0120 | 24 | | GK | | 29-0 | 34-45-01 | D40039J | | 41 | | | D42013P | 41 | | 001-002 | | |
| 0120 | 24 | | GK | | 28-0 | 34-45-01 | D40039J | | 41 | | | D42013P | 41 | | 115-199 | | |
| 0121 | 24 | | GK | | 29-0 | 34-45-01 | D40039J | | 45 | | | D42013P | 45 | | 001-002 | | |
| 0121 | 24 | | GK | | 28-0 | 34-45-01 | D40039J | | 45 | | | D42013P | 45 | | 115-199 | | |
| 0122 | 24 | | GK | | 29-0 | 34-45-01 | D40039J | | 46 | | | D42013P | 46 | | 001-099 | | |
| 0122 | 24 | | GK | | 28-0 | 34-45-01 | D40039J | | 46 | | | D42013P | 46 | | 115-199 | | |
| 0123 | 24 | | GK | | 29-0 | 34-45-01 | D40039J | | 47 | | | D42013P | 47 | | 001-099 | | |
| 0123 | 24 | | GK | | 28-0 | 34-45-01 | D40039J | | 47 | | | D42013P | 47 | | 115-199 | | |
| 0134 | 24 | | PK | | 34-0 | 34-61-18 | D40039J | | 26 | | | D42013P | 54 | | 115-199 | | |
| 1024 | 22 | | GA | | 3-0 | 34-45-01 | D40039J | | | AA | | GD01019 | ST.. | 2 | 001-002 | | |
| 1024 | 22 | | GA | | 3-0 | 34-45-01 | D40039J | | | AA | | GD01019 | S.. | 2 | 115-199 | | |
| 1025 | 22 | | GA | | 3-0 | 34-45-01 | D40039J | | | AB | | GD01019 | ST.. | 2 | ALL | | |
| 2001B | 22 | | GB | AA | 25-0 | 34-12-11 | D40039J | | 23 | | | D42011P | 23 | | 001-099 | | |
| 2001B | 22 | | GB | AB | 26-0 | 34-12-11 | D40039J | | 23 | | | D42011P | 23 | | 115-199 | | |
| 2001R | 22 | | GB | AA | 0-0 | 34-12-11 | D40039J | | 22 | | | D42011P | 22 | | 001-099 | | |
| 2001R | 22 | | GB | AB | 0-0 | 34-12-11 | D40039J | | 22 | | | D42011P | 22 | | 115-199 | | |
| 2002B | 22 | | GB | AB | 25-0 | SPARE | D40039J | | 14 | | | D42011P | 14 | | 001-099 | | |
| 2002B | 22 | | GB | AD | 26-0 | 34-12-11 | D40039J | | 14 | | | D42011P | 14 | | 115-199 | | |
| 2002R | 22 | | GB | AB | 0-0 | SPARE | D40039J | | 13 | | | D42011P | 13 | | 001-099 | | |
| 2002R | 22 | | GB | AD | 0-0 | 34-12-11 | D40039J | | 13 | | | D42011P | 13 | | 115-199 | | |
| 2004B | 22 | | GB | AD | 32-0 | 34-51-11 | D40629J | | 22 | | | D43009P | 5 | | 001-099 | | |
| 2004B | 22 | | GB | BX | 154-0 | 34-51-11 | D40629J | | 22 | | | D42001P | 5 | | 115-199 | | |
| 2004R | 22 | | GB | AD | 0-0 | 34-51-11 | D40629J | | 21 | | | D43009P | 4 | | 001-099 | | |
| 2004R | 22 | | GB | BX | 0-0 | 34-51-11 | D40629J | | 21 | | | D42001P | 4 | | 115-199 | | |
| 2508B | 24 | | G2 | AS | 41-0 | 77-12-31 | D40523J | | 1 | | | D42023P | 1 | | 001-099 | | |
| 2508B | 24 | | G2 | AS | 40-0 | SPARE | D40523J | | 1 | | | D42023P | 1 | | 115-199 | | |
| 2508R | 24 | | G2 | AS | 0-0 | 77-12-31 | D40523J | | 2 | | | D42023P | 2 | | 001-099 | | |
| 2508R | 24 | | G2 | AS | 0-0 | SPARE | D40523J | | 2 | | | D42023P | 2 | | 115-199 | | |
| 2508Z | | | | AS | 0-0 | 77-12-31 | D40523J | | 3 | | | D42023P | 3 | | 001-099 | | |
| 2508Z | | | | AS | 0-0 | SPARE | D40523J | | 3 | | | D42023P | 3 | | 115-199 | | |
| 2509B | 24 | | G2 | AT | 41-0 | SPARE | D40523J | | 4 | | | D42023P | 4 | | 001-099 | | |
| 2509B | 24 | | G2 | AY | 40-0 | 77-12-31 | D40523J | | 4 | | | D42023P | 4 | | 115-199 | | |
| 2509R | 24 | | G2 | AT | 0-0 | SPARE | D40523J | | 5 | | | D42023P | 5 | | 001-099 | | |
| 2509R | 24 | | G2 | AY | 0-0 | 77-12-31 | D40523J | | 5 | | | D42023P | 5 | | 115-199 | | |
| 2509Z | | | | AT | 0-0 | SPARE | D40523J | | 6 | | | D42023P | 6 | | 001-099 | | |
| 2509Z | | | | AY | 0-0 | 77-12-31 | D40523J | | 6 | | | D42023P | 6 | | 115-199 | | |
| 2512B | 24 | | G2 | BB | 26-0 | SPARE | D40039J | | 38 | | | D42011P | 42 | | 115-199 | | |
| 2512R | 24 | | G2 | BB | 0-0 | SPARE | D40039J | | 37 | | | D42011P | 41 | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2241 | 286N2241 | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | | |
| 2512Z | | | | BB | 0-0 | SPARE | D40039J | 39 | | | D42011P | 43 | | | 115-199 |
| 2518B | 24 | G2 | | BM | 28-0 | SPARE | D40523J | 39 | | | D42021P | 30 | | | 115-199 |
| 2518R | 24 | G2 | | BM | 0-0 | SPARE | D40523J | 38 | | | D42021P | 29 | | | 115-199 |
| 2518Z | | | | BM | 0-0 | SPARE | D40523J | 40 | | | D42021P | 31 | | | 115-199 |
| 2520B | 24 | G2 | | BE | 36-0 | SPARE | D40523J | 45 | | | D40639P | 16 | | | 001-099 |
| 2520B | 24 | G2 | | BJ | 36-0 | SPARE | D40523J | 45 | | | D40639P | 16 | | | 115-199 |
| 2520R | 24 | G2 | | BE | 0-0 | SPARE | D40523J | 44 | | | D40639P | 15 | | | 001-099 |
| 2520R | 24 | G2 | | BJ | 0-0 | SPARE | D40523J | 44 | | | D40639P | 15 | | | 115-199 |
| 2520Z | | | | BE | 0-0 | SPARE | D40523J | 46 | | | D40639P | 17 | | | 001-099 |
| 2520Z | | | | BJ | 0-0 | SPARE | D40523J | 46 | | | D40639P | 17 | | | 115-199 |
| 2525B | 24 | G2 | | CB | 28-0 | SPARE | D40629J | 30 | | | D42013P | 29 | | | 115-199 |
| 2525R | 24 | G2 | | CB | 0-0 | SPARE | D40629J | 29 | | | D42013P | 28 | | | 115-199 |
| 2525Z | | | | CB | 0-0 | SPARE | D40629J | 31 | | | D42013P | 30 | | | 115-199 |
| 2526B | 24 | G2 | | CC | 28-0 | SPARE | D40629J | 33 | | | D42013P | 20 | | | 115-199 |
| 2526R | 24 | G2 | | CC | 0-0 | SPARE | D40629J | 32 | | | D42013P | 19 | | | 115-199 |
| 2526Z | | | | CC | 0-0 | SPARE | D40629J | 34 | | | D42013P | 21 | | | 115-199 |
| 3001B | 24 | GM | | CA | 25-0 | 34-12-11 | D40039J | 20 | | | D42011P | 20 | | | 001-099 |
| 3001B | 24 | GM | | AA | 26-0 | 34-12-11 | D40039J | 20 | | | D42011P | 20 | | | 115-199 |
| 3001R | 24 | GM | | CA | 0-0 | 34-12-11 | D40039J | 19 | | | D42011P | 19 | | | 001-099 |
| 3001R | 24 | GM | | AA | 0-0 | 34-12-11 | D40039J | 19 | | | D42011P | 19 | | | 115-199 |
| 3001Y | 24 | GM | | CA | 0-0 | 34-12-11 | D40039J | 21 | | | D42011P | 21 | | | 001-099 |
| 3001Y | 24 | GM | | AA | 0-0 | 34-12-11 | D40039J | 21 | | | D42011P | 21 | | | 115-199 |
| 3002B | 24 | GM | | CB | 25-0 | SPARE | D40039J | 11 | | | D42011P | 11 | | | 001-099 |
| 3002B | 24 | GM | | AC | 26-0 | 34-12-11 | D40039J | 11 | | | D42011P | 11 | | | 115-199 |
| 3002R | 24 | GM | | CB | 0-0 | SPARE | D40039J | 10 | | | D42011P | 10 | | | 001-099 |
| 3002R | 24 | GM | | AC | 0-0 | 34-12-11 | D40039J | 10 | | | D42011P | 10 | | | 115-199 |
| 3002Y | 24 | GM | | CB | 0-0 | SPARE | D40039J | 12 | | | D42011P | 12 | | | 001-099 |
| 3002Y | 24 | GM | | AC | 0-0 | 34-12-11 | D40039J | 12 | | | D42011P | 12 | | | 115-199 |
| 3502B | 24 | G3 | | DB | 31-0 | 23-51-12 | D40629J | 41 | | | D42019P | 16 | | | 001-099 |
| 3502B | 24 | G3 | | CE | 31-0 | 23-51-12 | D40629J | 41 | | | D42019P | 16 | | | 115-199 |
| 3502R | 24 | G3 | | DB | 0-0 | 23-51-12 | D40629J | 40 | | | D42019P | 15 | | | 001-099 |
| 3502R | 24 | G3 | | CE | 0-0 | 23-51-12 | D40629J | 40 | | | D42019P | 15 | | | 115-199 |
| 3502Y | 24 | G3 | | DB | 0-0 | 23-51-12 | D40629J | 42 | | | D42019P | 17 | | | 001-099 |
| 3502Y | 24 | G3 | | CE | 0-0 | 23-51-12 | D40629J | 42 | | | D42019P | 17 | | | 115-199 |
| 3502Z | | | | DB | 0-0 | 23-51-12 | D40629J | 43 | | | D42019P | 18 | | | 001-099 |
| 3502Z | | | | CE | 0-0 | 23-51-12 | D40629J | 43 | | | D42019P | 18 | | | 115-199 |
| 5001B | 24 | G2 | | EA | 25-0 | 34-22-81 | D40031J | 23 | | | D42011P | 3 | | | 001-099 |
| 5001B | 24 | G2 | | AE | 25-0 | SPARE | D40031J | 23 | | | D42011P | 3 | | | 115-199 |
| 5001R | 24 | G2 | | EA | 0-0 | 34-22-81 | D40031J | 22 | | | D42011P | 2 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2241 | 286N2241 | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | | |
| 5001R | 24 | | G2 | AE | 0-0 | SPARE | D40031J | 22 | | | D42011P | 2 | | | 115-199 |
| 5001Z | | | | EA | 0-0 | 34-22-81 | D40031J | 24 | | | D42011P | 1 | | | 001-099 |
| 5001Z | | | | AE | 0-0 | SPARE | D40031J | 24 | | | D42011P | 1 | | | 115-199 |
| 5002B | 24 | | G2 | EB | 25-0 | 34-22-81 | D40031J | 42 | | | D42011P | 5 | | | 001-099 |
| 5002B | 24 | | G2 | AF | 25-0 | 34-22-83 | D40031J | 42 | | | D42011P | 5 | | | 115-199 |
| 5002R | 24 | | G2 | EB | 0-0 | 34-22-81 | D40031J | 41 | | | D42011P | 4 | | | 001-099 |
| 5002R | 24 | | G2 | AF | 0-0 | 34-22-83 | D40031J | 41 | | | D42011P | 4 | | | 115-199 |
| 5002Z | | | | EB | 0-0 | 34-22-81 | D40031J | 43 | | | D42011P | 6 | | | 001-099 |
| 5002Z | | | | AF | 0-0 | 34-22-83 | D40031J | 43 | | | D42011P | 6 | | | 115-199 |
| 5003B | 24 | | G2 | EC | 31-0 | 34-22-81 | D40031J | 33 | | | D43009P | 12 | | | 001-099 |
| 5003B | 24 | | G2 | AG | 153-0 | 34-22-83 | D40031J | 33 | | | D42001P | 7 | | | 115-199 |
| 5003R | 24 | | G2 | EC | 0-0 | 34-22-81 | D40031J | 32 | | | D43009P | 11 | | | 001-099 |
| 5003R | 24 | | G2 | AG | 0-0 | 34-22-83 | D40031J | 32 | | | D42001P | 6 | | | 115-199 |
| 5003Z | | | | EC | 0-0 | 34-22-81 | D40031J | 34 | | | D43009P | 13 | | | 001-099 |
| 5003Z | | | | AG | 0-0 | 34-22-83 | D40031J | 34 | | | D42001P | 8 | | | 115-199 |
| 5005B | 24 | | G2 | EE | 28-0 | 34-22-82 | D40031J | 36 | | | D42015P | 6 | | | 001-099 |
| 5005B | 24 | | G2 | AI | 28-0 | 34-22-82 | D40031J | 36 | | | D42015P | 6 | | | 115-199 |
| 5005R | 24 | | G2 | EE | 0-0 | 34-22-82 | D40031J | 35 | | | D42015P | 5 | | | 001-099 |
| 5005R | 24 | | G2 | AI | 0-0 | 34-22-82 | D40031J | 35 | | | D42015P | 5 | | | 115-199 |
| 5005Z | | | | EE | 0-0 | 34-22-82 | D40031J | 37 | | | D42015P | 7 | | | 001-099 |
| 5005Z | | | | AI | 0-0 | 34-22-82 | D40031J | 37 | | | D42015P | 7 | | | 115-199 |
| 5007B | 24 | | G2 | EG | 25-0 | 34-13-11 | D40031J | 26 | | | D42011P | 26 | | | 001-099 |
| 5007B | 24 | | G2 | AK | 25-0 | 34-13-11 | D40031J | 26 | | | D42011P | 26 | | | 115-199 |
| 5007R | 24 | | G2 | EG | 0-0 | 34-13-11 | D40031J | 25 | | | D42011P | 25 | | | 001-099 |
| 5007R | 24 | | G2 | AK | 0-0 | 34-13-11 | D40031J | 25 | | | D42011P | 25 | | | 115-199 |
| 5007Z | | | | EG | 0-0 | 34-13-11 | D40031J | 27 | | | D42011P | 27 | | | 001-099 |
| 5007Z | | | | AK | 0-0 | 34-13-11 | D40031J | 27 | | | D42011P | 27 | | | 115-199 |
| 5008B | 24 | | G2 | EH | 25-0 | SPARE | D40039J | 29 | | | D42011P | 29 | | | 001-099 |
| 5008B | 24 | | G2 | AL | 26-0 | SPARE | D40039J | 29 | | | D42011P | 29 | | | 115-199 |
| 5008R | 24 | | G2 | EH | 0-0 | SPARE | D40039J | 28 | | | D42011P | 28 | | | 001-099 |
| 5008R | 24 | | G2 | AL | 0-0 | SPARE | D40039J | 28 | | | D42011P | 28 | | | 115-199 |
| 5008Z | | | | EH | 0-0 | SPARE | D40039J | 30 | | | D42011P | 30 | | | 001-099 |
| 5008Z | | | | AL | 0-0 | SPARE | D40039J | 30 | | | D42011P | 30 | | | 115-199 |
| 5009B | 24 | | G2 | EI | 25-0 | 31-25-11 | D40031J | 45 | | | D42011P | 17 | | | 001-099 |
| 5009B | 24 | | G2 | AW | 25-0 | 31-25-11 | D40031J | 45 | | | D42011P | 45 | | | 115-199 |
| 5009R | 24 | | G2 | EI | 0-0 | 31-25-11 | D40031J | 44 | | | D42011P | 16 | | | 001-099 |
| 5009R | 24 | | G2 | AW | 0-0 | 31-25-11 | D40031J | 44 | | | D42011P | 44 | | | 115-199 |
| 5009Z | | | | EI | 0-0 | 31-25-11 | D40031J | 46 | | | D42011P | 18 | | | 001-099 |
| 5009Z | | | | AW | 0-0 | 31-25-11 | D40031J | 46 | | | D42011P | 46 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2241 | 286N2241 | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | | |
| 5010B | 24 | | G2 | AT | 25-0 | 34-22-28 | D40031J | | 51 | | D42011P | | 51 | | 115-199 |
| 5010R | 24 | | G2 | AT | 0-0 | 34-22-28 | D40031J | | 50 | | D42011P | | 50 | | 115-199 |
| 5010Z | | | | AT | 0-0 | 34-22-28 | D40031J | | 52 | | D42011P | | 52 | | 115-199 |
| 5011B | 24 | | G2 | EK | 41-0 | 77-11-11 | D40523J | | 21 | | D42023P | | 16 | | 001-099 |
| 5011B | 24 | | G2 | AZ | 40-0 | 77-11-11 | D40523J | | 21 | | D42023P | | 16 | | 115-199 |
| 5011R | 24 | | G2 | EK | 0-0 | 77-11-11 | D40523J | | 20 | | D42023P | | 15 | | 001-099 |
| 5011R | 24 | | G2 | AZ | 0-0 | 77-11-11 | D40523J | | 20 | | D42023P | | 15 | | 115-199 |
| 5011Z | | | | EK | 0-0 | 77-11-11 | D40523J | | 22 | | D42023P | | 17 | | 001-099 |
| 5011Z | | | | AZ | 0-0 | 77-11-11 | D40523J | | 22 | | D42023P | | 17 | | 115-199 |
| 5012B | 24 | | G2 | EL | 31-0 | SPARE | D40031J | | 54 | | D42019P | | 7 | | 001-099 |
| 5012R | 24 | | G2 | EL | 0-0 | SPARE | D40031J | | 53 | | D42019P | | 6 | | 001-099 |
| 5012Z | | | | EL | 0-0 | SPARE | D40031J | | 55 | | D42019P | | 8 | | 001-099 |
| 5014B | 24 | | G2 | EN | 28-0 | SPARE | D40031J | | 39 | | D42015P | | 9 | | 001-099 |
| 5014R | 24 | | G2 | EN | 0-0 | SPARE | D40031J | | 38 | | D42015P | | 8 | | 001-099 |
| 5014Z | | | | EN | 0-0 | SPARE | D40031J | | 40 | | D42015P | | 10 | | 001-099 |
| 5015B | 24 | | G2 | EO | 28-0 | 22-12-11 | D40629J | | 6 | | D42013P | | 6 | | 001-099 |
| 5015B | 24 | | G2 | BS | 28-0 | 22-12-11 | D40629J | | 6 | | D42013P | | 6 | | 115-199 |
| 5015R | 24 | | G2 | EO | 0-0 | 22-12-11 | D40629J | | 5 | | D42013P | | 5 | | 001-099 |
| 5015R | 24 | | G2 | BS | 0-0 | 22-12-11 | D40629J | | 5 | | D42013P | | 5 | | 115-199 |
| 5015Z | | | | EO | 0-0 | 22-12-11 | D40629J | | 7 | | D42013P | | 7 | | 001-099 |
| 5015Z | | | | BS | 0-0 | 22-12-11 | D40629J | | 7 | | D42013P | | 7 | | 115-199 |
| 5016B | 24 | | G2 | EP | 28-0 | 22-13-11 | D40629J | | 9 | | D42013P | | 9 | | 001-099 |
| 5016B | 24 | | G2 | BT | 28-0 | 22-13-11 | D40629J | | 9 | | D42013P | | 9 | | 115-199 |
| 5016R | 24 | | G2 | EP | 0-0 | 22-13-11 | D40629J | | 8 | | D42013P | | 8 | | 001-099 |
| 5016R | 24 | | G2 | BT | 0-0 | 22-13-11 | D40629J | | 8 | | D42013P | | 8 | | 115-199 |
| 5016Z | | | | EP | 0-0 | 22-13-11 | D40629J | | 10 | | D42013P | | 10 | | 001-099 |
| 5016Z | | | | BT | 0-0 | 22-13-11 | D40629J | | 10 | | D42013P | | 10 | | 115-199 |
| 5017B | 24 | | G2 | EQ | 31-0 | 34-55-11 | D40629J | | 12 | | D42019P | | 20 | | 001-099 |
| 5017B | 24 | | G2 | BU | 31-0 | 34-55-11 | D40629J | | 12 | | D42019P | | 20 | | 115-199 |
| 5017R | 24 | | G2 | EQ | 0-0 | 34-55-11 | D40629J | | 11 | | D42019P | | 19 | | 001-099 |
| 5017R | 24 | | G2 | BU | 0-0 | 34-55-11 | D40629J | | 11 | | D42019P | | 19 | | 115-199 |
| 5017Z | | | | EQ | 0-0 | 34-55-11 | D40629J | | 13 | | D42019P | | 21 | | 001-099 |
| 5017Z | | | | BU | 0-0 | 34-55-11 | D40629J | | 13 | | D42019P | | 21 | | 115-199 |
| 5018B | 24 | | G2 | ER | 28-0 | 34-51-11 | D40629J | | 16 | | D42013P | | 16 | | 001-099 |
| 5018B | 24 | | G2 | BV | 28-0 | 34-51-11 | D40629J | | 16 | | D42013P | | 16 | | 115-199 |
| 5018R | 24 | | G2 | ER | 0-0 | 34-51-11 | D40629J | | 15 | | D42013P | | 15 | | 001-099 |
| 5018R | 24 | | G2 | BV | 0-0 | 34-51-11 | D40629J | | 15 | | D42013P | | 15 | | 115-199 |
| 5018Z | | | | ER | 0-0 | 34-51-11 | D40629J | | 17 | | D42013P | | 17 | | 001-099 |
| 5018Z | | | | BV | 0-0 | 34-51-11 | D40629J | | 17 | | D42013P | | 17 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2241 | 286N2241 | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | | |
| 5019B | 24 | G2 | ES | | 32-0 | 34-51-11 | D40629J | 19 | | | D43009P | 2 | | | 001-099 |
| 5019B | 24 | G2 | BW | | 154-0 | 34-51-11 | D40629J | 19 | | | D42001P | 2 | | | 115-199 |
| 5019R | 24 | G2 | ES | | 0-0 | 34-51-11 | D40629J | 18 | | | D43009P | 1 | | | 001-099 |
| 5019R | 24 | G2 | BW | | 0-0 | 34-51-11 | D40629J | 18 | | | D42001P | 1 | | | 115-199 |
| 5019Z | | | ES | | 0-0 | 34-51-11 | D40629J | 20 | | | D43009P | 3 | | | 001-099 |
| 5019Z | | | BW | | 0-0 | 34-51-11 | D40629J | 20 | | | D42001P | 3 | | | 115-199 |
| 5020B | 24 | G2 | ET | | 27-0 | 34-31-11 | D40629J | 25 | | | D42021P | 25 | | | 001-099 |
| 5020B | 24 | G2 | CA | | 28-0 | 34-31-11 | D40629J | 25 | | | D42021P | 25 | | | 115-199 |
| 5020R | 24 | G2 | ET | | 0-0 | 34-31-11 | D40629J | 24 | | | D42021P | 24 | | | 001-099 |
| 5020R | 24 | G2 | CA | | 0-0 | 34-31-11 | D40629J | 24 | | | D42021P | 24 | | | 115-199 |
| 5020Z | | | ET | | 0-0 | 34-31-11 | D40629J | 26 | | | D42021P | 26 | | | 001-099 |
| 5020Z | | | CA | | 0-0 | 34-31-11 | D40629J | 26 | | | D42021P | 26 | | | 115-199 |
| 5021B | 24 | G2 | EU | | 28-0 | SPARE | D40629J | 45 | | | D42013P | 22 | | | 001-099 |
| 5021B | 24 | G2 | CF | | 28-0 | SPARE | D40629J | 45 | | | D42013P | 26 | | | 115-199 |
| 5021R | 24 | G2 | EU | | 0-0 | SPARE | D40629J | 44 | | | D42013P | 21 | | | 001-099 |
| 5021R | 24 | G2 | CF | | 0-0 | SPARE | D40629J | 44 | | | D42013P | 25 | | | 115-199 |
| 5021Z | | | EU | | 0-0 | SPARE | D40629J | 46 | | | D42013P | 23 | | | 001-099 |
| 5021Z | | | CF | | 0-0 | SPARE | D40629J | 46 | | | D42013P | 27 | | | 115-199 |
| 5022B | 24 | G2 | EV | | 36-0 | 22-14-11 | D40031J | 7 | | | D40639P | 7 | | | 001-099 |
| 5022B | 24 | G2 | AX | | 36-0 | 22-14-11 | D40031J | 7 | | | D40639P | 7 | | | 115-199 |
| 5022R | 24 | G2 | EV | | 0-0 | 22-14-11 | D40031J | 8 | | | D40639P | 8 | | | 001-099 |
| 5022R | 24 | G2 | AX | | 0-0 | 22-14-11 | D40031J | 8 | | | D40639P | 8 | | | 115-199 |
| 5022Z | | | EV | | 0-0 | 22-14-11 | D40031J | 9 | | | D40639P | 9 | | | 001-099 |
| 5022Z | | | AX | | 0-0 | 22-14-11 | D40031J | 9 | | | D40639P | 9 | | | 115-199 |
| 5024B | 24 | G2 | EX | | 28-0 | 22-14-11 | D40629J | 50 | | | D42021P | 13 | | | 001-099 |
| 5024B | 24 | G2 | CG | | 28-0 | 22-14-11 | D40629J | 50 | | | D42021P | 13 | | | 115-199 |
| 5024R | 24 | G2 | EX | | 0-0 | 22-14-11 | D40629J | 49 | | | D42021P | 12 | | | 001-099 |
| 5024R | 24 | G2 | CG | | 0-0 | 22-14-11 | D40629J | 49 | | | D42021P | 12 | | | 115-199 |
| 5024Z | | | EX | | 0-0 | 22-14-11 | D40629J | 51 | | | D42021P | 14 | | | 001-099 |
| 5024Z | | | CG | | 0-0 | 22-14-11 | D40629J | 51 | | | D42021P | 14 | | | 115-199 |
| 5025B | 24 | G2 | CH | | 32-0 | 31-31-42 | D40031J | 29 | | | D42019P | 29 | | | 001-099 |
| 5025B | 24 | G2 | CH | | 31-0 | 31-31-22 | D40031J | 29 | | | D42019P | 27 | | | 115-199 |
| 5025R | 24 | G2 | CH | | 0-0 | 31-31-42 | D40031J | 28 | | | D42019P | 28 | | | 001-099 |
| 5025R | 24 | G2 | CH | | 0-0 | 31-31-22 | D40031J | 28 | | | D42019P | 28 | | | 115-199 |
| 5025Z | | | CH | | 0-0 | 31-31-42 | D40031J | 30 | | | D42019P | 30 | | | 001-099 |
| 5025Z | | | CH | | 0-0 | 31-31-22 | D40031J | 30 | | | D42019P | 29 | | | 115-199 |
| 5028B | 24 | G2 | CK | | 26-0 | 34-55-11 | D40039J | 52 | | | D42011P | 48 | | | 115-199 |
| 5028R | 24 | G2 | CK | | 0-0 | 34-55-11 | D40039J | 51 | | | D42011P | 47 | | | 115-199 |
| 5028Z | | | CK | | 0-0 | 34-55-11 | D40039J | 53 | | | D42011P | 49 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2241 | 286N2241 | | | | AP0001 TO E-E BAY - LEFT (continued) | | | | | | | | | | |
| 5030B | 24 | | G2 | DA | 29-0 | 34-45-01 | D40039J | 43 | | | D42013P | 43 | | | 001-002 |
| 5030B | 24 | | G2 | DA | 28-0 | 34-45-01 | D40039J | 43 | | | D42013P | 43 | | | 115-199 |
| 5030R | 24 | | G2 | DA | 0-0 | 34-45-01 | D40039J | 42 | | | D42013P | 42 | | | 001-002, 115-199 |
| 5030Z | | | | DA | 0-0 | 34-45-01 | D40039J | | | AA | D42013P | 44 | | | 001-002, 115-199 |
| 5031B | 24 | | G2 | AF | 29-0 | 34-45-01 | D40039J | 39 | | | D42013P | 49 | | | 001-002 |
| 5031B | 24 | | G2 | AF | 29-0 | 34-45-01 | D40039J | 49 | | | D42013P | 49 | | | 003-099 |
| 5031B | 24 | | G2 | DB | 28-0 | 34-45-01 | D40039J | 49 | | | D42013P | 49 | | | 115-199 |
| 5031R | 24 | | G2 | AF | 0-0 | 34-45-01 | D40039J | 48 | | | D42013P | 48 | | | 001-099 |
| 5031R | 24 | | G2 | DB | 0-0 | 34-45-01 | D40039J | 48 | | | D42013P | 48 | | | 115-199 |
| 5031Z | | | | AF | 0-0 | 34-45-01 | D40039J | | | AB | D42013P | 50 | | | 001-099 |
| 5031Z | | | | DB | 0-0 | 34-45-01 | D40039J | | | AB | D42013P | 50 | | | 115-199 |
| FRAA | | | | | 0-0 | 34-45-01 | D40039J | | | AA | D40039J | 44 | | | 001-002, 115-199 |
| FRAB | | | | | 0-0 | 34-45-01 | D40039J | | | AB | D40039J | 50 | | | 001-099 |
| FRAB | | | | | 0-0 | 34-45-01 | D40039J | | | AB | D40039J | 55 | | | 115-199 |
| W2243 | 286N2243 | | | | AP0001 TO E-E BAY - RIGHT | | | | | | | | | | |
| 0001 | 24 | | GK | | 43-0 | SPARE | D40077J | 10 | | | D42041P | 10 | | | 001-099 |
| 0001 | 22 | | GA | | 43-0 | SPARE | D40077J | 10 | | | D42041P | 10 | | | 115-199 |
| 0002 | 22 | | GA | | 43-0 | 29-21-32 | D40077J | 14 | | | D42041P | 17 | | | ALL |
| 0003 | 22 | | GA | | 40-0 | 22-41-13 | D40077J | 23 | | | D42035P | 23 | | | 001-099 |
| 0003 | 22 | | GA | | 39-5 | 22-41-13 | D40077J | 23 | | | D42035P | 23 | | | 115-199 |
| 0004 | 22 | | GA | | 40-0 | 34-61-25 | D40077J | 52 | | | D42035P | 14 | | | 001-099 |
| 0007 | 22 | | GA | | 40-0 | 22-14-11 | D40077J | 49 | | | D42035P | 7 | | | 001-099 |
| 0007 | 22 | | GA | | 39-5 | 22-14-11 | D40077J | 49 | | | D42035P | 7 | | | 115-199 |
| 0008 | 22 | | GA | | 40-0 | 22-14-11 | D40077J | 50 | | | D42035P | 8 | | | 001-099 |
| 0008 | 22 | | GA | | 39-5 | 22-14-11 | D40077J | 50 | | | D42035P | 8 | | | 115-199 |
| 0009 | 22 | | GA | | 39-5 | SPARE | D40077J | 51 | | | D42035P | 9 | | | 115-199 |
| 0014 | 22 | | GA | | 43-0 | 32-42-12 | D40077J | 39 | | | D42041P | 24 | | | ALL |
| 0018 | 22 | | GA | | 43-0 | 79-33-11 | D40077J | 38 | | | D42041P | 18 | | | ALL |
| 0020 | 22 | | GA | | 39-5 | SPARE | D40077J | 53 | | | D42035P | 32 | | | 115-199 |
| 0021 | 22 | | GA | | 39-5 | SPARE | D40077J | 54 | | | D42035P | 33 | | | 115-199 |
| 0026 | 24 | | PK | | 40-0 | 34-61-18 | D40077J | 11 | | | D42035P | 5 | | | 115-199 |
| 0095 | 24 | | GK | | 34-10 | 34-55-21 | D40077J | 55 | | | D42039P | 1 | | | 115-199 |
| 0096 | 24 | | GK | | 40-0 | 34-12-22 | D40077J | 40 | | | D42035P | 4 | | | 001-099 |
| 0096 | 24 | | GK | | 39-5 | 34-12-22 | D40077J | 40 | | | D42035P | 34 | | | 115-199 |
| 0097 | 22 | | GA | | 39-5 | SPARE | D40077J | 41 | | | D42035P | 35 | | | 115-199 |
| 0098 | 22 | | GA | | 39-5 | SPARE | D40077J | 42 | | | D42035P | 36 | | | 115-199 |
| 2001B | 22 | | GB | AA | 40-0 | 34-12-21 | D40077J | 28 | | | D42035P | 28 | | | 001-099 |
| 2001B | 22 | | GB | AB | 39-5 | 34-12-21 | D40077J | 28 | | | D42035P | 28 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---------------------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2243 | 286N2243 | | | AP0001 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | |
| 2001R | 22 | GB | AA | 0-0 | 34-12-21 | D40077J | | 27 | | | D42035P | 27 | | | 001-099 |
| 2001R | 22 | GB | AB | 0-0 | 34-12-21 | D40077J | | 27 | | | D42035P | 27 | | | 115-199 |
| 2002B | 22 | GB | AB | 40-0 | SPARE | D40077J | | 22 | | | D42035P | 22 | | | 001-099 |
| 2002B | 22 | GB | AD | 39-5 | 34-12-21 | D40077J | | 22 | | | D42035P | 22 | | | 115-199 |
| 2002R | 22 | GB | AB | 0-0 | SPARE | D40077J | | 21 | | | D42035P | 21 | | | 001-099 |
| 2002R | 22 | GB | AD | 0-0 | 34-12-21 | D40077J | | 21 | | | D42035P | 21 | | | 115-199 |
| 2502B | 24 | G2 | BB | 43-0 | 77-12-31 | D40077J | | 7 | | | D42041P | 8 | | | 001-099 |
| 2502B | 24 | G2 | AH | 43-0 | SPARE | D40077J | | 8 | | | D42041P | 8 | | | 115-199 |
| 2502R | 24 | G2 | BB | 0-0 | 77-12-31 | D40077J | | 8 | | | D42041P | 7 | | | 001-099 |
| 2502R | 24 | G2 | AH | 0-0 | SPARE | D40077J | | 7 | | | D42041P | 7 | | | 115-199 |
| 2502Z | | | BB | 0-0 | 77-12-31 | D40077J | | 9 | | | D42041P | 9 | | | 001-099 |
| 2502Z | | | AH | 0-0 | SPARE | D40077J | | 9 | | | D42041P | 9 | | | 115-199 |
| 2504B | 24 | G2 | BD | 43-0 | SPARE | D40077J | | 30 | | | D42041P | 2 | | | 001-099 |
| 2504B | 24 | G2 | AJ | 43-0 | 77-12-31 | D40077J | | 30 | | | D42041P | 30 | | | 115-199 |
| 2504R | 24 | G2 | BD | 0-0 | SPARE | D40077J | | 29 | | | D42041P | 1 | | | 001-099 |
| 2504R | 24 | G2 | AJ | 0-0 | 77-12-31 | D40077J | | 29 | | | D42041P | 29 | | | 115-199 |
| 2504Z | | | BD | 0-0 | SPARE | D40077J | | 31 | | | D42041P | 3 | | | 001-099 |
| 2504Z | | | AJ | 0-0 | 77-12-31 | D40077J | | 31 | | | D42041P | 31 | | | 115-199 |
| 2508B | 24 | G2 | AR | 43-0 | SPARE | D40077J | | 47 | | | D42041P | 20 | | | 115-199 |
| 2508R | 24 | G2 | AR | 0-0 | SPARE | D40077J | | 46 | | | D42041P | 19 | | | 115-199 |
| 2508Z | | | AR | 0-0 | SPARE | D40077J | | 48 | | | D42041P | 21 | | | 115-199 |
| 3001B | 24 | GM | CA | 40-0 | 34-12-21 | D40077J | | 25 | | | D42035P | 25 | | | 001-099 |
| 3001B | 24 | GM | AA | 39-5 | 34-12-21 | D40077J | | 25 | | | D42035P | 25 | | | 115-199 |
| 3001R | 24 | GM | CA | 0-0 | 34-12-21 | D40077J | | 24 | | | D42035P | 24 | | | 001-099 |
| 3001R | 24 | GM | AA | 0-0 | 34-12-21 | D40077J | | 24 | | | D42035P | 24 | | | 115-199 |
| 3001Y | 24 | GM | CA | 0-0 | 34-12-21 | D40077J | | 26 | | | D42035P | 26 | | | 001-099 |
| 3001Y | 24 | GM | AA | 0-0 | 34-12-21 | D40077J | | 26 | | | D42035P | 26 | | | 115-199 |
| 3002B | 24 | GM | CB | 40-0 | SPARE | D40077J | | 19 | | | D42035P | 19 | | | 001-099 |
| 3002B | 24 | GM | AC | 39-5 | 34-12-21 | D40077J | | 19 | | | D42035P | 19 | | | 115-199 |
| 3002R | 24 | GM | CB | 0-0 | SPARE | D40077J | | 18 | | | D42035P | 18 | | | 001-099 |
| 3002R | 24 | GM | AC | 0-0 | 34-12-21 | D40077J | | 18 | | | D42035P | 18 | | | 115-199 |
| 3002Y | 24 | GM | CB | 0-0 | SPARE | D40077J | | 20 | | | D42035P | 20 | | | 001-099 |
| 3002Y | 24 | GM | AC | 0-0 | 34-12-21 | D40077J | | 20 | | | D42035P | 20 | | | 115-199 |
| 5001B | 24 | G2 | EA | 40-0 | 34-13-11 | D40077J | | 3 | | | D42035P | 3 | | | 001-099 |
| 5001B | 24 | G2 | AE | 39-5 | 34-13-11 | D40077J | | 3 | | | D42035P | 3 | | | 115-199 |
| 5001R | 24 | G2 | EA | 0-0 | 34-13-11 | D40077J | | 2 | | | D42035P | 2 | | | 001-099 |
| 5001R | 24 | G2 | AE | 0-0 | 34-13-11 | D40077J | | 2 | | | D42035P | 2 | | | 115-199 |
| 5001Z | | | EA | 0-0 | 34-13-11 | D40077J | | 1 | | | D42035P | 1 | | | 001-099 |
| 5001Z | | | AE | 0-0 | 34-13-11 | D40077J | | 1 | | | D42035P | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2243 | 286N2243 | | | AP0001 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | | |
| 5002B | 24 | G2 | EB | 40-0 | 34-22-81 | D40077J | 16 | | | | D42035P | 30 | | | 001-099 | |
| 5002B | 24 | G2 | AF | 39-5 | 34-22-83 | D40077J | 16 | | | | D42035P | 30 | | | 115-199 | |
| 5002R | 24 | G2 | EB | 0-0 | 34-22-81 | D40077J | 15 | | | | D42035P | 29 | | | 001-099 | |
| 5002R | 24 | G2 | AF | 0-0 | 34-22-83 | D40077J | 15 | | | | D42035P | 29 | | | 115-199 | |
| 5002Z | | | EB | 0-0 | 34-22-81 | D40077J | 17 | | | | D42035P | 31 | | | 001-099 | |
| 5002Z | | | AF | 0-0 | 34-22-83 | D40077J | 17 | | | | D42035P | 31 | | | 115-199 | |
| 5003B | 24 | G2 | EC | 43-0 | 77-11-11 | D40077J | 5 | | | | D42041P | 5 | | | 001-099 | |
| 5003B | 24 | G2 | AG | 43-0 | 77-11-11 | D40077J | 5 | | | | D42041P | 5 | | | 115-199 | |
| 5003R | 24 | G2 | EC | 0-0 | 77-11-11 | D40077J | 4 | | | | D42041P | 4 | | | 001-099 | |
| 5003R | 24 | G2 | AG | 0-0 | 77-11-11 | D40077J | 4 | | | | D42041P | 4 | | | 115-199 | |
| 5003Z | | | EC | 0-0 | 77-11-11 | D40077J | 6 | | | | D42041P | 6 | | | 001-099 | |
| 5003Z | | | AG | 0-0 | 77-11-11 | D40077J | 6 | | | | D42041P | 6 | | | 115-199 | |
| 5006B | 24 | G2 | AQ | 34-10 | SPARE | D40077J | 36 | | | | D42039P | 5 | | | 115-199 | |
| 5006R | 24 | G2 | AQ | 0-0 | SPARE | D40077J | 35 | | | | D42039P | 4 | | | 115-199 | |
| 5006Z | | | AQ | 0-0 | SPARE | D40077J | 37 | | | | D42039P | 6 | | | 115-199 | |
| W2244 | 286N2244 | | | P6 TO E/E AREA - RIGHT BUSESSES | | | | | | | | | | | | |
| 0001 | 22 | GA | | 34-0 | SPARE | D40286P | CAP | Y | | | D40894P | 5 | | | 001-002, 115-199 | |
| 0002 | 22 | GA | | 34-0 | SPARE | D40286P | 6 | | | | D40894P | 6 | | | ALL | |
| 0003 | 16 | GA | | 31-0 | 78-34-61 | D40286P | 5 | 16 | | | SP01942 | | 9 | | ALL | |
| 0007 | 24 | GK | | 33-0 | 24-34-11 | D40286P | 7 | | | | D40892P | 7 | | | 001-099 | |
| 0007 | 22 | GA | | 33-0 | 24-34-11 | D40286P | 7 | | | | D40892P | 7 | | | 115-199 | |
| 0008 | 24 | GK | | 33-0 | 24-34-11 | D40286P | 8 | | | | D40892P | 8 | | | 001-099 | |
| 0008 | 22 | GA | | 33-0 | 24-34-11 | D40286P | 8 | | | | D40892P | 8 | | | 115-199 | |
| 0009 | 22 | GA | | 33-0 | SPARE | D40286P | 9 | | | | D40892P | 9 | | | ALL | |
| 0010 | 22 | GA | | 33-0 | SPARE | D40286P | 10 | | | | D40892P | 10 | | | ALL | |
| 0014 | 24 | GK | | 29-0 | 24-34-11 | D40286P | 12 | | | | D41122P | 15 | | | 001-099 | |
| 0014 | 22 | GA | | 29-0 | 24-34-11 | D40286P | 12 | | | | D41122P | 14 | | | 115-199 | |
| 0015 | 16 | GA | | 5-0 | 24-32-11 | D01860 | 5 | | | | GD00512 | ST.. | E | | ALL | |
| 0016 | 14 | GA | | 31-0 | 24-32-11 | D40250P | 6 | | | | D01860 | 8 | | | ALL | |
| 0017 | 14 | GA | | 31-0 | 24-32-11 | D40250P | 7 | | | | D01860 | 7 | | | ALL | |
| 0018 | 14 | GA | | 31-0 | 24-32-11 | D40250P | 8 | | | | D01860 | 6 | | | ALL | |
| 0019 | 14 | GA | | 20-0 | 27-51-11 | D40250P | 9 | | | | D41418P | 4 | | | ALL | |
| 0020 | 14 | GA | | 20-0 | 27-51-11 | D40250P | 10 | | | | D41418P | 5 | | | ALL | |
| 0021 | 14 | GA | | 20-0 | 27-51-11 | D40250P | 11 | | | | D41418P | 6 | | | ALL | |
| 0022 | 14 | GA | | 20-0 | 27-81-11 | D40250P | 12 | | | | D41418P | 3 | | | ALL | |
| 0023 | 14 | GA | | 20-0 | 27-81-11 | D40250P | 3 | | | | D41418P | 1 | | | ALL | |
| 0024 | 14 | GA | | 20-0 | 27-81-11 | D40250P | 4 | | | | D41418P | 2 | | | ALL | |
| 0025 | 14 | GA | | 20-0 | 24-53-21 | D40250P | 5 | | | | D41418P | 11 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2244 | 286N2244 | | | P6 TO E/E AREA - RIGHT BUSESSE (continued) | | | | | | | | | | | | |
| 0032 | 20 | GA | | | 20-0 | 24-53-21 | D40250P | | 2 | | | D41418P | 12 | | | ALL |
| 0041 | 20 | GA | | | 19-0 | 30-41-12 | D41122P | | 1 | | | D41756P | 1 | | | 001-099 |
| 0041 | 18 | GA | | | 19-0 | 30-41-12 | D41122P | | 1 | | | D41756P | 1 | | | 115-199 |
| 0042 | 20 | GA | | | 19-0 | 30-41-12 | D41122P | | 2 | | | D41756P | 2 | | | 001-099 |
| 0042 | 18 | GA | | | 19-0 | 30-41-12 | D41122P | | 2 | | | D41756P | 2 | | | 115-199 |
| 0043 | 20 | GA | | | 29-0 | 30-33-11 | D40250P | | 1 | | | D41122P | 3 | | | ALL |
| 0057 | 16 | GA | | | 19-0 | SPARE | D41122P | | 7 | | | D41756P | 7 | | | 115-199 |
| 0058 | 16 | GA | | | 19-0 | SPARE | D41122P | | 8 | | | D41756P | 8 | | | 115-199 |
| 0066 | 16 | GA | | | 27-0 | 21-58-13 | D40294P | | 1 | | | D40920P | 6 | | | 115-199 |
| 0067 | 16 | GA | | | 27-0 | 21-58-13 | D40294P | | 2 | | | D40920P | 7 | | | 115-199 |
| 0068 | 16 | GA | | | 27-0 | 21-58-13 | D40294P | | 3 | | | D40920P | 8 | | | 115-199 |
| 0254 | 24 | GK | | | 17-0 | 24-27-21 | D40892P | | 4 | | | D40894P | 14 | | | ALL |
| 0255 | 24 | GK | | | 21-0 | 24-27-21 | D40892P | | 5 | | | D41122P | 5 | | | ALL |
| 0256 | 24 | GK | | | 21-0 | 24-27-21 | D40892P | | 6 | | | D41122P | 6 | | | ALL |
| 0257 | 22 | GA | | | 29-0 | 24-32-41 | D40286P | | 11 | | | D41122P | 4 | | | ALL |
| 0601 | 14 | GA | | | 27-0 | SPARE | D40294P | | 4 | | | D40920P | 3 | | | 115-199 |
| 0602 | 14 | GA | | | 27-0 | SPARE | D40294P | | 5 | | | D40920P | 4 | | | 115-199 |
| 0603 | 14 | GA | | | 27-0 | SPARE | D40294P | | 6 | | | D40920P | 5 | | | 115-199 |
| 0604 | 20 | GA | | | 19-0 | SPARE | D41756P | | 9 | | | D41122P | 9 | | | 115-199 |
| 0605 | 20 | GA | | | 19-0 | SPARE | D41756P | | 10 | | | D41122P | 10 | | | 115-199 |
| 0606 | 20 | GA | | | 19-0 | SPARE | D41756P | | 11 | | | D41122P | 11 | | | 115-199 |
| 0607 | 20 | GA | | | 19-0 | SPARE | D41756P | | 12 | | | D41122P | 12 | | | 115-199 |
| 0609 | 20 | GA | | | 21-0 | SPARE | D41122P | | 13 | | | D40892P | 13 | | | 115-199 |
| 0610 | 20 | GA | | | 17-0 | SPARE | D40892P | | 14 | | | D40894P | 13 | | | 115-199 |
| 2001B | 24 | GL | BA | | 24-0 | 24-34-11 | SP00604 | | 9 | | | D40892P | 1 | | | 001-099 |
| 2001B | 22 | GB | BA | | 24-0 | 24-34-11 | SP00604 | | 9 | | | D40892P | 1 | | | 115-199 |
| 2001R | 24 | GL | BA | | 0-0 | 24-34-11 | SP00606 | | 9 | | | D40892P | 2 | | | 001-099 |
| 2001R | 22 | GB | BA | | 0-0 | 24-34-11 | SP00606 | | 9 | | | D40892P | 2 | | | 115-199 |
| 2002B | 24 | GL | BB | | 28-0 | 24-34-11 | D01860 | | 4 | | | D40892P | 11 | | | 001-099 |
| 2002B | 22 | GB | BB | | 28-0 | 24-34-11 | D01860 | | 4 | | | D40892P | 11 | | | 115-199 |
| 2002R | 24 | GL | BB | | 0-0 | 24-34-11 | D01860 | | 3 | | | D40892P | 12 | | | 001-099 |
| 2002R | 22 | GB | BB | | 0-0 | 24-34-11 | D01860 | | 3 | | | D40892P | 12 | | | 115-199 |
| 2003B | 12 | GB | BC | | 17-9 | 30-41-12 | D41122P | | 16 | | | D41756P | 4 | | | 001-099 |
| 2003B | 12 | GB | BC | | 16-1 | 30-41-12 | D40920P | | 1 | | | D41756P | 4 | | | 115-199 |
| 2003R | 12 | GB | BC | | 0-0 | 30-41-12 | D41122P | | 18 | | | D41756P | 5 | | | 001-099 |
| 2003R | 12 | GB | BC | | 0-0 | 30-41-12 | D40920P | | 2 | | | D41756P | 5 | | | 115-199 |
| 4004B | 24 | GN | AA | | 34-0 | 24-23-11 | D40286P | | 3 | | | D40894P | 3 | | | ALL |
| 4004G | 24 | GN | AA | | 0-0 | 24-23-11 | D40286P | | 4 | | | D40894P | 4 | | | ALL |
| 4004R | 24 | GN | AA | | 0-0 | 24-23-11 | D40286P | | 1 | | | D40894P | 1 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-------------|---|----|-----|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2244 | 286N2244 | P6 TO E/E AREA - RIGHT BUSSES (continued) | | | | | | | | | | | | | |
| 4004Y | 24 | GN | AA | | 0-0 | 24-23-11 | D40286P | | 2 | | D40894P | | 2 | | ALL |
| W2245 | 286N2245 | AP0001 TO E-E BAY CENTER | | | | | | | | | | | | | |
| 0001 | 24 | GK | | | 29-0 | 34-21-31 | D42047J | | 1 | | D42051P | | 1 | | ALL |
| 0002 | 24 | GK | | | 28-0 | 34-22-37 | D42047J | | 2 | | D42049P | | 22 | | 001-099 |
| 0002 | 24 | GK | | | 27-0 | 34-22-37 | D42047J | | 2 | | D42049P | | 22 | | 115-199 |
| 0003 | 24 | GK | | | 29-0 | 34-22-37 | D42047J | | 23 | | D42049P | | 19 | | 001-099 |
| 0003 | 24 | GK | | | 27-0 | 34-22-37 | D42047J | | 23 | | D42049P | | 19 | | 115-199 |
| 0004 | 22 | GA | | | 29-0 | 22-11-32 | D40633J | | 4 | | D42049P | | 15 | | ALL |
| 0005 | 22 | GA | | | 29-0 | 22-11-32 | D40633J | | 5 | | D42049P | | 16 | | ALL |
| 0006 | 22 | GA | | | 29-0 | SPARE | D40633J | | 6 | | D42049P | | 17 | | 001-099 |
| 0006 | 22 | GA | | | 29-0 | 22-11-32 | D40633J | | 6 | | D42049P | | 17 | | 115-199 |
| 0007 | 22 | GA | | | 29-0 | 22-14-11 | D42047J | | 18 | | D42049P | | 34 | | 001-099 |
| 0007 | 22 | GA | | | 27-0 | 22-14-11 | D42047J | | 18 | | D42049P | | 34 | | 115-199 |
| 0008 | 22 | GA | | | 29-0 | 22-14-11 | D42047J | | 19 | | D42049P | | 35 | | 001-099 |
| 0008 | 22 | GA | | | 27-0 | 22-14-11 | D42047J | | 19 | | D42049P | | 35 | | 115-199 |
| 0009 | 22 | GA | | | 29-0 | 22-14-11 | D42047J | | 6 | | D42049P | | 14 | | 001-099 |
| 0009 | 22 | GA | | | 27-0 | 22-14-11 | D42047J | | 6 | | D42049P | | 14 | | 115-199 |
| 0010 | 22 | GA | | | 28-0 | SPARE | D40633J | | 10 | | D42049P | | 30 | | 115-199 |
| 0011 | 22 | GA | | | 28-0 | SPARE | D40633J | | 11 | | D42049P | | 31 | | 115-199 |
| 0012 | 22 | GA | | | 29-0 | SPARE | D42047J | | 37 | | D42051P | | 3 | | ALL |
| 0013 | 22 | GA | | | 28-0 | SPARE | D42047J | | 38 | | D42051P | | 4 | | 115-199 |
| 0014 | 22 | GA | | | 28-0 | SPARE | D42047J | | 39 | | D42051P | | 5 | | 115-199 |
| 0015 | 22 | GA | | | 29-0 | 34-22-36 | D42047J | | 20 | | D42049P | | 40 | | 001-099 |
| 0015 | 22 | GA | | | 27-0 | 34-22-36 | D42047J | | 20 | | D42049P | | 40 | | 115-199 |
| 0016 | 22 | GA | | | 29-0 | SPARE | D42047J | | 24 | | D42049P | | 18 | | 001-099 |
| 0016 | 22 | GA | | | 27-0 | SPARE | D42047J | | 24 | | D42049P | | 18 | | 115-199 |
| 0017 | 24 | GK | | | 29-0 | 34-24-11 | D42047J | | 50 | | D42049P | | 36 | | 001-099 |
| 0017 | 24 | GK | | | 27-0 | 34-24-11 | D42047J | | 50 | | D42049P | | 36 | | 115-199 |
| 0018 | 24 | GK | | | 29-0 | 34-24-11 | D42047J | | 51 | | D42049P | | 37 | | 001-099 |
| 0018 | 24 | GK | | | 27-0 | 34-24-11 | D42047J | | 51 | | D42049P | | 37 | | 115-199 |
| 0019 | 24 | GK | | | 29-0 | 34-24-11 | D42047J | | 52 | | D42049P | | 38 | | 001-099 |
| 0019 | 24 | GK | | | 27-0 | 34-24-11 | D42047J | | 52 | | D42049P | | 38 | | 115-199 |
| 0020 | 24 | GK | | | 29-0 | 34-24-11 | D42047J | | 53 | | D42049P | | 39 | | 001-099 |
| 0020 | 24 | GK | | | 27-0 | 34-24-11 | D42047J | | 53 | | D42049P | | 39 | | 115-199 |
| 2001B | 24 | GL | AA | | 29-0 | SPARE | D42047J | | 22 | | D42049P | | 20 | | 001-099 |
| 2001B | 24 | GL | AB | | 27-0 | SPARE | D42047J | | 22 | | D42049P | | 20 | | 115-199 |
| 2001R | 24 | GL | AA | | 0-0 | SPARE | D42047J | | 21 | | D42049P | | 21 | | 001-099 |
| 2001R | 24 | GL | AB | | 0-0 | SPARE | D42047J | | 21 | | D42049P | | 21 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--------------------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2245 | 286N2245 | | | AP0001 TO E-E BAY CENTER (continued) | | | | | | | | | | | |
| 2002B | 24 | GL | AB | 29-0 | 34-24-11 | D42047J | | 8 | | | D42049P | 7 | | | 001-099 |
| 2002B | 24 | GL | AC | 27-0 | 34-24-11 | D42047J | | 8 | | | D42049P | 7 | | | 115-199 |
| 2002R | 24 | GL | AB | 0-0 | 34-24-11 | D42047J | | 7 | | | D42049P | 6 | | | 001-099 |
| 2002R | 24 | GL | AC | 0-0 | 34-24-11 | D42047J | | 7 | | | D42049P | 6 | | | 115-199 |
| 2003B | 24 | GL | AC | 29-0 | 34-24-11 | D42047J | | 10 | | | D42049P | 9 | | | 001-099 |
| 2003B | 24 | GL | AD | 27-0 | 34-24-11 | D42047J | | 10 | | | D42049P | 9 | | | 115-199 |
| 2003R | 24 | GL | AC | 0-0 | 34-24-11 | D42047J | | 9 | | | D42049P | 8 | | | 001-099 |
| 2003R | 24 | GL | AD | 0-0 | 34-24-11 | D42047J | | 9 | | | D42049P | 8 | | | 115-199 |
| 2004B | 24 | GL | AD | 29-0 | 34-24-11 | D42047J | | 14 | | | D42049P | 11 | | | 001-099 |
| 2004B | 24 | GL | AE | 27-0 | 34-24-11 | D42047J | | 14 | | | D42049P | 11 | | | 115-199 |
| 2004R | 24 | GL | AD | 0-0 | 34-24-11 | D42047J | | 13 | | | D42049P | 10 | | | 001-099 |
| 2004R | 24 | GL | AE | 0-0 | 34-24-11 | D42047J | | 13 | | | D42049P | 10 | | | 115-199 |
| 2005B | 24 | GL | AE | 29-0 | 34-24-11 | D42047J | | 12 | | | D42049P | 13 | | | 001-099 |
| 2005B | 24 | GL | AF | 27-0 | 34-24-11 | D42047J | | 12 | | | D42049P | 13 | | | 115-199 |
| 2005R | 24 | GL | AE | 0-0 | 34-24-11 | D42047J | | 11 | | | D42049P | 12 | | | 001-099 |
| 2005R | 24 | GL | AF | 0-0 | 34-24-11 | D42047J | | 11 | | | D42049P | 12 | | | 115-199 |
| 2006B | 22 | GB | AF | 29-0 | 34-24-11 | D42047J | | 33 | | | D42049P | 5 | | | 001-099 |
| 2006B | 22 | GB | AK | 27-0 | 34-24-11 | D42047J | | 33 | | | D42049P | 5 | | | 115-199 |
| 2006R | 22 | GB | AF | 0-0 | 34-24-11 | D42047J | | 32 | | | D42049P | 4 | | | 001-099 |
| 2006R | 22 | GB | AK | 0-0 | 34-24-11 | D42047J | | 32 | | | D42049P | 4 | | | 115-199 |
| 3001B | 22 | GC | CA | 29-0 | 34-24-11 | D42047J | | 4 | | | D42049P | 2 | | | 001-099 |
| 3001B | 22 | GC | AA | 27-0 | 34-24-11 | D42047J | | 4 | | | D42049P | 2 | | | 115-199 |
| 3001R | 22 | GC | CA | 0-0 | 34-24-11 | D42047J | | 3 | | | D42049P | 1 | | | 001-099 |
| 3001R | 22 | GC | AA | 0-0 | 34-24-11 | D42047J | | 3 | | | D42049P | 1 | | | 115-199 |
| 3001Y | 22 | GC | CA | 0-0 | 34-24-11 | D42047J | | 5 | | | D42049P | 3 | | | 001-099 |
| 3001Y | 22 | GC | AA | 0-0 | 34-24-11 | D42047J | | 5 | | | D42049P | 3 | | | 115-199 |
| 5001B | 24 | G2 | EA | 29-0 | 34-22-82 | D42047J | | 29 | | | D42051P | 9 | | | 001-099 |
| 5001B | 24 | G2 | AG | 29-0 | 34-22-82 | D42047J | | 29 | | | D42051P | 29 | | | 115-199 |
| 5001R | 24 | G2 | EA | 0-0 | 34-22-82 | D42047J | | 28 | | | D42051P | 8 | | | 001-099 |
| 5001R | 24 | G2 | AG | 0-0 | 34-22-82 | D42047J | | 28 | | | D42051P | 28 | | | 115-199 |
| 5001Z | | | EA | 0-0 | 34-22-82 | D42047J | | 30 | | | D42051P | 10 | | | 001-099 |
| 5001Z | | | AG | 0-0 | 34-22-82 | D42047J | | 30 | | | D42051P | 30 | | | 115-199 |
| 5002B | 24 | G2 | EB | 29-0 | 34-22-81 | D42047J | | 15 | | | D42051P | 5 | | | 001-099 |
| 5002B | 24 | G2 | AH | 28-0 | 34-22-83 | D42047J | | 15 | | | D42051P | 15 | | | 115-199 |
| 5002R | 24 | G2 | EB | 0-0 | 34-22-81 | D42047J | | 16 | | | D42051P | 6 | | | 001-099 |
| 5002R | 24 | G2 | AH | 0-0 | 34-22-83 | D42047J | | 16 | | | D42051P | 16 | | | 115-199 |
| 5002Z | | | EB | 0-0 | 34-22-81 | D42047J | | 17 | | | D42051P | 7 | | | 001-099 |
| 5002Z | | | AH | 0-0 | 34-22-83 | D42047J | | 17 | | | D42051P | 17 | | | 115-199 |
| 5003B | 24 | G2 | EC | 29-0 | 22-12-31 | D40633J | | 2 | | | D42049P | 23 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2245 | 286N2245 | | | | AP0001 TO E-E BAY CENTER (continued) | | | | | | | | | | |
| 5003B | 24 | G2 | AI | | 29-0 | 22-12-31 | D40633J | 2 | | | D42049P | 23 | | | 115-199 |
| 5003R | 24 | G2 | EC | | 0-0 | 22-12-31 | D40633J | 1 | | | D42049P | 24 | | | 001-099 |
| 5003R | 24 | G2 | AI | | 0-0 | 22-12-31 | D40633J | 1 | | | D42049P | 24 | | | 115-199 |
| 5003Z | | | EC | | 0-0 | 22-12-31 | D40633J | 3 | | | D42049P | 25 | | | 001-099 |
| 5003Z | | | AI | | 0-0 | 22-12-31 | D40633J | 3 | | | D42049P | 25 | | | 115-199 |
| 5004B | 24 | G2 | ED | | 29-0 | SPARE | D40633J | 8 | | | D42049P | 28 | | | 001-099 |
| 5004B | 24 | G2 | AJ | | 29-0 | SPARE | D40633J | 8 | | | D42049P | 28 | | | 115-199 |
| 5004R | 24 | G2 | ED | | 0-0 | SPARE | D40633J | 7 | | | D42049P | 27 | | | 001-099 |
| 5004R | 24 | G2 | AJ | | 0-0 | SPARE | D40633J | 7 | | | D42049P | 27 | | | 115-199 |
| 5004Z | | | ED | | 0-0 | SPARE | D40633J | 9 | | | D42049P | 29 | | | 001-099 |
| 5004Z | | | AJ | | 0-0 | SPARE | D40633J | 9 | | | D42049P | 29 | | | 115-199 |
| 5005B | 24 | G2 | EE | | 29-0 | SPARE | D42047J | 26 | | | D42051P | 12 | | | 001-099 |
| 5005B | 24 | G2 | AL | | 29-0 | SPARE | D42047J | 26 | | | D42051P | 26 | | | 115-199 |
| 5005R | 24 | G2 | EE | | 0-0 | SPARE | D42047J | 25 | | | D42051P | 11 | | | 001-099 |
| 5005R | 24 | G2 | AL | | 0-0 | SPARE | D42047J | 25 | | | D42051P | 25 | | | 115-199 |
| 5005Z | | | EE | | 0-0 | SPARE | D42047J | 27 | | | D42051P | 4 | | | 001-099 |
| 5005Z | | | AL | | 0-0 | SPARE | D42047J | 27 | | | D42051P | 27 | | | 115-199 |
| 5006B | 24 | G2 | AM | | 28-0 | SPARE | D42047J | 35 | | | D42051P | 23 | | | 115-199 |
| 5006R | 24 | G2 | AM | | 0-0 | SPARE | D42047J | 34 | | | D42051P | 22 | | | 115-199 |
| 5006Z | | | AM | | 0-0 | SPARE | D42047J | 36 | | | D42051P | 24 | | | 115-199 |
| W2247 | 286N2247 | | | | AP0003 TO E-E BAY,STANDBY | | | | | | | | | | |
| 0001 | 22 | GA | | | 35-0 | 26-17-11 | D42165J | 1 | | | D42167P | 1 | | | ALL |
| 0002 | 22 | GA | | | 35-0 | 22-14-21 | D42165J | 2 | | | D42167P | 2 | | | ALL |
| 0003 | 22 | GA | | | 35-0 | 22-41-13 | D42165J | 3 | | | D42167P | 3 | | | ALL |
| 0005 | 20 | GA | | | 41-0 | 32-35-11 | D42165J | 5 | 18 | | D42169P | 5 | 18 | | 001-099 |
| 0005 | 18 | GA | | | 42-0 | 32-35-11 | D42165J | 5 | 18 | | D42169P | 5 | 18 | | 115-199 |
| 0006 | 20 | GA | | | 41-0 | 32-35-11 | D42165J | 6 | 18 | | D42169P | 6 | 18 | | 001-099 |
| 0006 | 18 | GA | | | 42-0 | 32-35-11 | D42165J | 6 | 18 | | D42169P | 6 | 18 | | 115-199 |
| 0007 | 20 | GA | | | 41-0 | 32-35-11 | D42165J | 7 | 18 | | D42169P | 7 | 18 | | 001-099 |
| 0007 | 18 | GA | | | 42-0 | 32-35-11 | D42165J | 7 | 18 | | D42169P | 7 | 18 | | 115-199 |
| 0008 | 24 | GK | | | 41-0 | 32-41-11 | D42165J | 8 | | | D42169P | 8 | | | 001-099 |
| 0008 | 24 | GK | | | 42-0 | 32-41-11 | D42165J | 8 | | | D42169P | 8 | | | 115-199 |
| 0009 | 24 | GK | | | 41-0 | 32-41-11 | D42165J | 9 | | | D42169P | 9 | | | 001-099 |
| 0009 | 24 | GK | | | 42-0 | 32-41-11 | D42165J | 9 | | | D42169P | 9 | | | 115-199 |
| 0010 | 24 | GK | | | 41-0 | 32-41-11 | D42165J | 10 | | | D42169P | 10 | | | 001-099 |
| 0010 | 24 | GK | | | 42-0 | 32-41-11 | D42165J | 10 | | | D42169P | 10 | | | 115-199 |
| 0011 | 24 | GK | | | 41-0 | 32-41-11 | D42165J | 11 | | | D42169P | 11 | | | 001-099 |
| 0011 | 24 | GK | | | 42-0 | 32-41-11 | D42165J | 11 | | | D42169P | 11 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2247 | 286N2247 | | | AP0003 TO E-E BAY,STANDBY (continued) | | | | | | | | | | | |
| 0012 | 22 | | GA | | 35-0 | SPARE | D42165J | | 12 | | D42167P | | 5 | | 001, 003-099, 115-199 |
| 0012 | 22 | | GA | | 35-0 | 34-25-12 | D42165J | | 12 | | D42167P | | 5 | | 002 |
| 0013 | 22 | | GA | | 35-0 | SPARE | D42165J | | 13 | | D42167P | | 6 | | 115-199 |
| 0014 | 22 | | GA | | 35-0 | SPARE | D42165J | | 14 | | D42167P | | 7 | | 115-199 |
| 0015 | 22 | | GA | | 35-0 | SPARE | D42165J | | 15 | | D42167P | | 8 | | 115-199 |
| 0016 | 18 | | GA | | 41-0 | SPARE | D42165J | | 16 | 18 | D42169P | | 1 | 18 | 001-099 |
| 0016 | 18 | | GA | | 42-0 | 32-35-11 | D42165J | | 16 | 18 | D42169P | | 1 | 18 | 115-199 |
| 0017 | 22 | | GA | | 42-0 | SPARE | D42165J | | 17 | | D42169P | | 2 | | 115-199 |
| 0018 | 22 | | GA | | 42-0 | SPARE | D42165J | | 18 | | D42169P | | 3 | | 115-199 |
| 0019 | 22 | | GA | | 42-0 | SPARE | D42165J | | 19 | | D42169P | | 4 | | 115-199 |
| 0020 | 22 | | GA | | 42-0 | SPARE | D42165J | | 20 | | D42169P | | 12 | | 115-199 |
| 0021 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 48 | | D42053P | | 9 | | 001-099 |
| 0021 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 48 | | D42053P | | 9 | | 115-199 |
| 0022 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 49 | | D42053P | | 10 | | 001-099 |
| 0022 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 49 | | D42053P | | 10 | | 115-199 |
| 0023 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 40 | | D42053P | | 11 | | 001-099 |
| 0023 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 40 | | D42053P | | 11 | | 115-199 |
| 0024 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 41 | | D42053P | | 12 | | 001-099 |
| 0024 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 41 | | D42053P | | 12 | | 115-199 |
| 0025 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 42 | | D42053P | | 13 | | 001-099 |
| 0025 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 42 | | D42053P | | 13 | | 115-199 |
| 0026 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 43 | | D42053P | | 14 | | 001-099 |
| 0026 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 43 | | D42053P | | 14 | | 115-199 |
| 0027 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 44 | | D42053P | | 15 | | 001-099 |
| 0027 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 44 | | D42053P | | 15 | | 115-199 |
| 0028 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 45 | | D42053P | | 6 | | 001-099 |
| 0028 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 45 | | D42053P | | 6 | | 115-199 |
| 0029 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 46 | | D42053P | | 7 | | 001-099 |
| 0029 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 46 | | D42053P | | 7 | | 115-199 |
| 0030 | 24 | | GK | | 39-0 | 27-51-61 | D42165J | | 47 | | D42053P | | 8 | | 001-099 |
| 0030 | 22 | | GA | | 39-0 | 27-51-61 | D42165J | | 47 | | D42053P | | 8 | | 115-199 |
| 0031 | 22 | | GA | | 39-0 | SPARE | D42165J | | 36 | | D42053P | | 1 | | ALL |
| 0032 | 22 | | GA | | 39-0 | SPARE | D42165J | | 37 | | D42053P | | 2 | | 115-199 |
| 0033 | 22 | | GA | | 39-0 | SPARE | D42165J | | 38 | | D42053P | | 3 | | 115-199 |
| 0034 | 22 | | GA | | 39-0 | SPARE | D42165J | | 39 | | D42053P | | 4 | | 115-199 |
| 0035 | 22 | | GA | | 35-0 | 22-14-21 | D42165J | | 35 | | D42167P | | 9 | | ALL |
| 0036 | 22 | | GA | | 35-0 | 22-14-21 | D42165J | | 4 | | D42167P | | 4 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2240

Page 17 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2250 | 286N2250 | | | P6 TO E/E AREA - BATTERY BUS | | | | | | | | | | | |
| 0001 | 24 | | GK | | 34-0 | 24-28-11 | D40246P | | 3 | | D40904P | | 3 | | ALL |
| 0002 | 20 | | GA | | 34-0 | 24-11-11 | D40246P | | 5 | | D41894P | | 5 | | 001-099 |
| 0002 | 20 | | GA | | 35-0 | 24-11-11 | D40246P | | 5 | | D41894P | | 5 | | 115-199 |
| 0003 | 20 | | GA | | 36-0 | 24-22-41 | D40246P | | 7 | | D41920P | | 1 | | 001-099 |
| 0003 | 20 | | GA | | 37-0 | 24-22-41 | D40246P | | 7 | | D41896P | | 7 | | 115-199 |
| 0006 | 20 | | GA | | 36-0 | 24-11-21 | D40246P | | 9 | | D40908P | | 9 | | ALL |
| 0007 | 20 | | GA | | 36-0 | 24-41-11 | D40246P | | 14 | | D41896P | | 4 | | 001-099 |
| 0007 | 20 | | GA | | 37-0 | 24-41-11 | D40246P | | 14 | | D41896P | | 4 | | 115-199 |
| 0008 | 16 | | GA | | 7-0 | SPARE | D40908P | | 10 | | D41894P | | 4 | | 001-099 |
| 0008 | 16 | | GA | | 8-0 | SPARE | D40908P | | 10 | | D41894P | | 4 | | 115-199 |
| 0010 | 24 | | GK | | 34-0 | 24-34-11 | D40246P | | 20 | | D40904P | | 1 | | 001-099 |
| 0010 | 22 | | GA | | 34-0 | 24-34-11 | D40246P | | 20 | | D40904P | | 1 | | 115-199 |
| 0011 | 24 | | GK | | 34-0 | 24-34-11 | D40246P | | 21 | | D40904P | | 5 | | 001-099 |
| 0011 | 22 | | GA | | 34-0 | 24-34-11 | D40246P | | 21 | | D40904P | | 5 | | 115-199 |
| 0012 | 22 | | GA | | 34-0 | SPARE | D40246P | | 25 | | D40904P | | 4 | | ALL |
| 0013 | 22 | | GA | | 34-0 | SPARE | D40246P | | 24 | | D40904P | | 6 | | 115-199 |
| 0014 | 24 | | GK | | 34-0 | 24-34-11 | D40246P | | 26 | | D40904P | | 2 | | 001-099 |
| 0014 | 22 | | GA | | 34-0 | 24-34-11 | D40246P | | 26 | | D40904P | | 2 | | 115-199 |
| 0015 | 22 | | GA | | 34-0 | 24-33-12 | D40246P | | 15 | | D40904P | | 6 | | 001-099 |
| 0015 | 22 | | GA | | 34-0 | SPARE | D40246P | | 15 | | D40904P | | 15 | | 115-199 |
| 0017 | 18 | | GA | | 34-0 | SPARE | D40246P | | 10 | | D41894P | | 10 | | 001-099 |
| 0017 | 18 | | GA | | 35-0 | SPARE | D40246P | | 10 | | D41894P | | 10 | | 115-199 |
| 0028 | 20 | | GA | | 34-0 | SPARE | D40246P | | 30 | | D40904P | | 10 | | 115-199 |
| 0029 | 20 | | GA | | 34-0 | SPARE | D40246P | | 29 | | D40904P | | 9 | | 115-199 |
| 0031 | 18 | | GA | | 36-0 | SPARE | D40246P | | 8 | | D40908P | | 7 | | ALL |
| 0032 | 18 | | GA | | 37-0 | 32-35-11 | D40246P | | 22 | 18 | SP01110 | | 9 | | 001-099 |
| 0032 | 20 | | GA | | 37-0 | 32-35-11 | D40246P | | 22 | | SP01110 | | 9 | | 115-199 |
| 0040 | 22 | | GA | | 34-0 | 24-51-72 | D40246P | | 32 | | D40904P | | 12 | | ALL |
| 0051 | 14 | | GA | | 30-0 | 34-21-11 | D40246P | | 1 | | D42225P | | 1 | | ALL |
| 0054 | 14 | | GA | | 31-0 | 34-21-31 | TB5011 | | 7 | E | D42229P | | 3 | | ALL |
| 0055 | 20 | | GA | | 34-0 | SPARE | D40246P | | 13 | | D40904P | | 14 | | 115-199 |
| 0072 | 24 | | GK | | 7-0 | 24-11-11 | D40908P | | 2 | | D41894P | | 2 | | 001-099 |
| 0072 | 24 | | GK | | 8-0 | 24-11-11 | D40908P | | 2 | | D41894P | | 2 | | 115-199 |
| 0520 | 14 | | GA | | 31-0 | 34-21-21 | TB5011 | | 6 | E | D42227P | | 2 | | ALL |
| 0601 | 22 | | GA | | 34-0 | 24-51-72 | D40246P | | 31 | | D40904P | | 11 | | 001-099 |
| 0601 | 20 | | GA | | 34-0 | 24-51-72 | D40246P | | 31 | | D40904P | | 11 | | 115-199 |
| 0603 | 20 | | GA | | 34-0 | SPARE | D40246P | | 18 | | D41894P | | 3 | | 001-099 |
| 0603 | 20 | | GA | | 35-0 | SPARE | D40246P | | 18 | | D41894P | | 3 | | 115-199 |
| 0604 | 20 | | GA | | 36-0 | SPARE | D40246P | | 19 | | D40908P | | 3 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2250 | 286N2250 | | | P6 TO E/E AREA - BATTERY BUS (continued) | | | | | | | | | | | |
| 0607 | 20 | | GA | | 8-0 | SPARE | D41894P | 6 | | | D40908P | 5 | | | 115-199 |
| 0608 | 20 | | GA | | 8-0 | SPARE | D41894P | 7 | | | D40908P | 6 | | | 115-199 |
| 0609 | 20 | | GA | | 8-0 | SPARE | D40908P | 8 | | | D41896P | 6 | | | 115-199 |
| 0610 | 20 | | GA | | 8-0 | SPARE | D40908P | 11 | | | D41896P | 8 | | | 115-199 |
| 0611 | 20 | | GA | | 8-0 | SPARE | D40908P | 12 | | | D41896P | 9 | | | 115-199 |
| 1052 | 20 | | GT | AD | 3-0 | 34-21-11 | SP01032 | | 9 | | D41758P | 2 | | | ALL |
| 1052Z | | | | AD | 0-0 | 34-21-11 | SP01032 | DED | | | D41758P | DED | | | ALL |
| 2007B | 24 | | GL | AA | 34-0 | 24-34-11 | D40246P | 28 | | | D40904P | 8 | | | 001-099 |
| 2007B | 22 | | GB | AA | 34-0 | 24-34-11 | D40246P | 28 | | | D40904P | 8 | | | 115-199 |
| 2007R | 24 | | GL | AA | 0-0 | 24-34-11 | D40246P | 27 | | | D40904P | 7 | | | 001-099 |
| 2007R | 22 | | GB | AA | 0-0 | 24-34-11 | D40246P | 27 | | | D40904P | 7 | | | 115-199 |
| W2251 | 286N2251 | | | AP0003 TO E-E BAY - LEFT | | | | | | | | | | | |
| 0003 | 22 | | GA | | 39-0 | 31-41-14 | D40035J | 32 | | | D42073P | 14 | | | ALL |
| 0004 | 22 | | GA | | 39-0 | SPARE | D40035J | 33 | | | D42073P | 12 | | | ALL |
| 0005 | 22 | | GA | | 39-0 | SPARE | D40035J | 34 | | | D42073P | 13 | | | 115-199 |
| 0006 | 22 | | GA | | 33-0 | SPARE | D40035J | 13 | | | D42065P | 15 | | | 115-199 |
| 0008 | 22 | | GA | | 33-0 | 22-41-13 | D40035J | 19 | | | D42065P | 12 | | | ALL |
| 0009 | 24 | | GK | | 33-0 | SPARE | D40035J | 29 | | | D42065P | 16 | | | 115-199 |
| 0010 | 22 | | GA | | 40-0 | 32-61-12 | D40035J | 34 | | | D42071P | 10 | | | 001-099 |
| 0010 | 22 | | GA | | 40-0 | 32-61-12 | D40035J | 36 | | | D42071P | 10 | | | 115-199 |
| 0011 | 24 | | GK | | 40-0 | 32-61-12 | D40035J | 35 | | | D42071P | 11 | | | ALL |
| 0012 | 24 | | GK | | 39-0 | 27-58-11 | D40035J | 52 | | | D42073P | 3 | | | 001-099 |
| 0012 | 22 | | GA | | 39-0 | 27-58-11 | D40035J | 52 | | | D42073P | 3 | | | 115-199 |
| 0013 | 24 | | GK | | 39-0 | 27-58-11 | D40035J | 53 | | | D42073P | 4 | | | 001-099 |
| 0013 | 22 | | GA | | 39-0 | 27-58-11 | D40035J | 53 | | | D42073P | 4 | | | 115-199 |
| 0014 | 24 | | GK | | 39-0 | 27-58-11 | D40035J | 54 | | | D42073P | 5 | | | 001-099 |
| 0014 | 22 | | GA | | 39-0 | 27-58-11 | D40035J | 54 | | | D42073P | 5 | | | 115-199 |
| 0015 | 24 | | GK | | 39-0 | 27-58-11 | D40035J | 55 | | | D42073P | 6 | | | 001-099 |
| 0015 | 22 | | GA | | 39-0 | 27-58-11 | D40035J | 55 | | | D42073P | 6 | | | 115-199 |
| 0016 | 24 | | GK | | 40-0 | 27-51-41 | D40035J | 20 | | | D42069P | 1 | | | 001-099 |
| 0016 | 22 | | GA | | 40-0 | 27-51-41 | D40035J | 20 | | | D42069P | 1 | | | 115-199 |
| 0017 | 24 | | GK | | 40-0 | 27-51-41 | D40035J | 21 | | | D42069P | 2 | | | 001-099 |
| 0017 | 22 | | GA | | 40-0 | 27-51-41 | D40035J | 21 | | | D42069P | 2 | | | 115-199 |
| 0018 | 22 | | GA | | 39-0 | 32-61-21 | D40035J | 49 | | | D42073P | 7 | | | ALL |
| 0019 | 22 | | GA | | 39-0 | 32-61-21 | D40035J | 50 | | | D42073P | 8 | | | ALL |
| 0020 | 22 | | GA | | 39-0 | 32-61-21 | D40035J | 51 | | | D42073P | 9 | | | ALL |
| 0021 | 22 | | GA | | 40-0 | SPARE | D40035J | 22 | | | D42069P | 3 | | | 115-199 |
| 0022 | 24 | | GK | | 40-0 | SPARE | D40035J | 7 | | | D42071P | 7 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2251 | 286N2251 | | | AP0003 TO E-E BAY - LEFT (continued) | | | | | | | | | | | |
| 0023 | 22 | | GA | | 40-0 | SPARE | D40035J | | 8 | | D42071P | | 8 | | 115-199 |
| 0024 | 22 | | GA | | 40-0 | SPARE | D40035J | | 9 | | D42071P | | 9 | | ALL |
| 0025 | 24 | | GK | | 39-0 | 77-12-11 | D40035J | | 22 | | D42073P | | 24 | | 001-099 |
| 0025 | 24 | | GK | | 39-0 | 77-12-11 | D42055J | | 28 | | D42073P | | 10 | | 115-199 |
| 0026 | 22 | | GA | | 39-0 | SPARE | D40035J | | 48 | | D42073P | | 11 | | 115-199 |
| 0027 | 22 | | GA | | 39-0 | 32-46-11 | D40035J | | 23 | | D42073P | | 1 | | 115-199 |
| 0028 | 22 | | GA | | 39-0 | 31-41-14 | D40035J | | 31 | | D42073P | | 2 | | ALL |
| 0029 | 22 | | GA | | 40-0 | SPARE | D40035J | | 14 | | D42069P | | 6 | | 115-199 |
| 0030 | 22 | | GA | | 40-0 | SPARE | D40035J | | 15 | | D42069P | | 7 | | 115-199 |
| 0031 | 22 | | GA | | 40-0 | SPARE | D42055J | | 5 | | D42069P | | 4 | | 115-199 |
| 0032 | 22 | | GA | | 40-0 | SPARE | D42055J | | 4 | | D42069P | | 5 | | 115-199 |
| 0033 | 22 | | GA | | 40-0 | 32-61-12 | D40035J | | 39 | | D42071P | | 1 | | ALL |
| 0034 | 24 | | GK | | 40-0 | 32-61-12 | D40035J | | 40 | | D42071P | | 2 | | ALL |
| 0035 | 22 | | GA | | 40-0 | SPARE | D40035J | | 41 | | D42071P | | 3 | | 115-199 |
| 0036 | 24 | | PK | | 31-1 | 34-61-18 | D42055J | | 13 | | D42065P | | 17 | | 115-199 |
| 0038 | 22 | | CQ | | 37-0 | 34-25-12 | D42055J | | 8 | | D42065P | | 18 | | 002 |
| 0041 | 24 | | GK | | 33-0 | 34-45-01 | D42055J | | 41 | | D42065P | | 41 | | 001-002 |
| 0041 | 24 | | GK | | 33-0 | 34-45-01 | D42055J | | 32 | | D42065P | | 32 | | 115-199 |
| 0042 | 24 | | GK | | 33-0 | 34-45-01 | D42055J | | 45 | | D42065P | | 45 | | 001-099 |
| 0042 | 24 | | GK | | 33-0 | 34-45-01 | D42055J | | 36 | | D42065P | | 36 | | 115-199 |
| 0043 | 24 | | GK | | 33-0 | 34-45-01 | D42055J | | 47 | | D42065P | | 47 | | 001-002 |
| 0043 | 24 | | GK | | 33-0 | 34-45-01 | D42055J | | 38 | | D42065P | | 38 | | 115-199 |
| 0044 | 24 | | GK | | 33-0 | 34-45-01 | D42055J | | 46 | | D42065P | | 46 | | 001-099 |
| 0044 | 24 | | GK | | 33-0 | 34-45-01 | D42055J | | 37 | | D42065P | | 37 | | 115-199 |
| 0045 | 22 | | GA | | 4-0 | 34-45-01 | D42055J | | | AF | GD01248 | ST.. | 2 | | 001-002 |
| 0045 | 22 | | GA | | 4-0 | 34-45-01 | D42055J | | | AM | GD01248 | ST.. | 2 | | 115-199 |
| 0046 | 22 | | GA | | 4-0 | 34-45-01 | D42055J | | | AG | GD01248 | ST.. | 2 | | ALL |
| 0050 | 22 | | GA | | 40-0 | SPARE | D42055J | | 8 | | D42069P | | 8 | | 115-199 |
| 0051 | 22 | | GA | | 40-0 | SPARE | D42055J | | 9 | | D42069P | | 11 | | 115-199 |
| 0052 | 22 | | GA | | 40-0 | SPARE | D42055J | | 7 | | D42069P | | 10 | | 115-199 |
| 0053 | 22 | | GA | | 40-0 | SPARE | D42055J | | 6 | | D42069P | | 9 | | 115-199 |
| 0054 | 24 | | GK | | 40-0 | 34-55-11 | D42055J | | 16 | | D42071P | | 12 | | 115-199 |
| 0057 | 22 | | GA | | 40-0 | SPARE | D42055J | | 25 | | D42071P | | 16 | | 115-199 |
| 0058 | 22 | | GA | | 40-0 | SPARE | D42055J | | 26 | | D42071P | | 17 | | 115-199 |
| 0059 | 22 | | GA | | 40-0 | SPARE | D42055J | | 27 | | D42071P | | 18 | | 115-199 |
| 2001B | 22 | | GB | AA | 33-0 | 34-12-11 | D40035J | | 28 | | D42065P | | 8 | | 001-099 |
| 2001B | 22 | | GB | AB | 33-0 | 34-12-11 | D40035J | | 28 | | D42065P | | 8 | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 34-12-11 | D40035J | | 27 | | D42065P | | 7 | | 001-099 |
| 2001R | 22 | | GB | AB | 0-0 | 34-12-11 | D40035J | | 27 | | D42065P | | 7 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|---|-------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2251 | 286N2251 | AP0003 TO E-E BAY - LEFT (continued) | | | | | | | | | | | | | |
| 2002B | 24 | GL | AB | 34-0 | 22-31-12 | D42055J | 18 | | D42063P | 10 | | | 001-099 | | |
| 2002B | 24 | GL | AR | 34-0 | 22-31-12 | D42055J | 18 | | D42063P | 10 | | | 115-199 | | |
| 2002R | 24 | GL | AB | 0-0 | 22-31-12 | D42055J | 17 | | D42063P | 9 | | | 001-099 | | |
| 2002R | 24 | GL | AR | 0-0 | 22-31-12 | D42055J | 17 | | D42063P | 9 | | | 115-199 | | |
| 2003B | 24 | GL | AC | 34-0 | 22-31-12 | D42055J | 20 | | D42063P | 6 | | | 001-099 | | |
| 2003B | 24 | GL | AP | 34-0 | 22-31-12 | D42055J | 20 | | D42063P | 6 | | | 115-199 | | |
| 2003R | 24 | GL | AC | 0-0 | 22-31-12 | D42055J | 19 | | D42063P | 5 | | | 001-099 | | |
| 2003R | 24 | GL | AP | 0-0 | 22-31-12 | D42055J | 19 | | D42063P | 5 | | | 115-199 | | |
| 2004B | 22 | GB | AD | 34-0 | 22-31-12 | D42055J | 22 | | D42063P | 8 | | | 001-099 | | |
| 2004B | 22 | GB | AQ | 34-0 | 22-31-12 | D42055J | 22 | | D42063P | 8 | | | 115-199 | | |
| 2004R | 22 | GB | AD | 0-0 | 22-31-12 | D42055J | 21 | | D42063P | 7 | | | 001-099 | | |
| 2004R | 22 | GB | AQ | 0-0 | 22-31-12 | D42055J | 21 | | D42063P | 7 | | | 115-199 | | |
| 2005B | 22 | GB | AE | 33-0 | SPARE | D40035J | 15 | | D42065P | 13 | | | 001-099 | | |
| 2005B | 22 | GB | AI | 33-0 | SPARE | D40035J | 38 | | D42065P | 13 | | | 115-199 | | |
| 2005R | 22 | GB | AE | 0-0 | SPARE | D40035J | 14 | | D42065P | 14 | | | 001-099 | | |
| 2005R | 22 | GB | AI | 0-0 | SPARE | D40035J | 37 | | D42065P | 14 | | | 115-199 | | |
| 2006B | 22 | GB | AS | 34-0 | SPARE | D42055J | 24 | | D42063P | 15 | | | 115-199 | | |
| 2006R | 22 | GB | AS | 0-0 | SPARE | D42055J | 23 | | D42063P | 14 | | | 115-199 | | |
| 2501B | 24 | G2 | BA | 39-0 | 77-12-11 | D40035J | 46 | | D42073P | 22 | | | 001-099 | | |
| 2501B | 24 | G2 | AO | 34-0 | SPARE | D40035J | 46 | | D42063P | 12 | | | 115-199 | | |
| 2501R | 24 | G2 | BA | 0-0 | 77-12-11 | D40035J | 45 | | D42073P | 21 | | | 001-099 | | |
| 2501R | 24 | G2 | AO | 0-0 | SPARE | D40035J | 45 | | D42063P | 11 | | | 115-199 | | |
| 2501Z | | | BA | 0-0 | 77-12-11 | D40035J | 47 | | D42073P | 23 | | | 001-099 | | |
| 2501Z | | | AO | 0-0 | SPARE | D40035J | 47 | | D42063P | 13 | | | 115-199 | | |
| 2504B | 24 | G2 | AL | 39-0 | 77-12-11 | D42055J | 30 | | D42073P | 19 | | | 115-199 | | |
| 2504R | 24 | G2 | AL | 0-0 | 77-12-11 | D42055J | 29 | | D42073P | 18 | | | 115-199 | | |
| 2504Z | | | AL | 0-0 | 77-12-11 | D42055J | 31 | | D42073P | 20 | | | 115-199 | | |
| 3001B | 24 | GM | CA | 33-0 | 34-12-11 | D40035J | 25 | | D42065P | 10 | | | 001-099 | | |
| 3001B | 24 | GM | AA | 33-0 | 34-12-11 | D40035J | 25 | | D42065P | 10 | | | 115-199 | | |
| 3001R | 24 | GM | CA | 0-0 | 34-12-11 | D40035J | 24 | | D42065P | 9 | | | 001-099 | | |
| 3001R | 24 | GM | AA | 0-0 | 34-12-11 | D40035J | 24 | | D42065P | 9 | | | 115-199 | | |
| 3001Y | 24 | GM | CA | 0-0 | 34-12-11 | D40035J | 26 | | D42065P | 11 | | | 001-099 | | |
| 3001Y | 24 | GM | AA | 0-0 | 34-12-11 | D40035J | 26 | | D42065P | 11 | | | 115-199 | | |
| 4501G | 22 | DU | DA | 39-0 | 77-21-11 | D42055J | 3 | | D42073P | 16 | | | 001-099 | | |
| 4501G | 20 | DU | AV | 39-0 | 77-21-11 | D42055J | 3 | TC | D42073P | 16 | TC | | 115-199 | | |
| 4501W | 22 | DU | DA | 0-0 | 77-21-11 | D42055J | 2 | | D42073P | 15 | | | 001-099 | | |
| 4501W | 20 | DU | AV | 0-0 | 77-21-11 | D42055J | 2 | TD | D42073P | 15 | TD | | 115-199 | | |
| 4501Z | | | DA | 0-0 | 77-21-11 | D42055J | 1 | | D42073P | 17 | | | 001-099 | | |
| 4501Z | | | AV | 0-0 | 77-21-11 | D42055J | 1 | | D42073P | 17 | | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2251 | 286N2251 | | | AP0003 TO E-E BAY - LEFT (continued) | | | | | | | | | | | | |
| 5001B | 24 | G2 | EA | | 34-0 | 34-22-91 | D40035J | 2 | | | D42063P | 17 | | | 001-099 | |
| 5001B | 24 | G2 | AE | | 34-0 | 34-22-93 | D40035J | 2 | | | D42063P | 17 | | | 115-199 | |
| 5001R | 24 | G2 | EA | | 0-0 | 34-22-91 | D40035J | 1 | | | D42063P | 16 | | | 001-099 | |
| 5001R | 24 | G2 | AE | | 0-0 | 34-22-93 | D40035J | 1 | | | D42063P | 16 | | | 115-199 | |
| 5001Z | | | EA | | 0-0 | 34-22-91 | D40035J | 3 | | | D42063P | 18 | | | 001-099 | |
| 5001Z | | | AE | | 0-0 | 34-22-93 | D40035J | 3 | | | D42063P | 18 | | | 115-199 | |
| 5002B | 24 | G2 | EB | | 33-0 | 34-13-21 | D40035J | 5 | | | D42065P | 5 | | | 001-099 | |
| 5002B | 24 | G2 | AC | | 33-0 | 34-13-21 | D40035J | 5 | | | D42065P | 5 | | | 115-199 | |
| 5002R | 24 | G2 | EB | | 0-0 | 34-13-21 | D40035J | 4 | | | D42065P | 4 | | | 001-099 | |
| 5002R | 24 | G2 | AC | | 0-0 | 34-13-21 | D40035J | 4 | | | D42065P | 4 | | | 115-199 | |
| 5002Z | | | EB | | 0-0 | 34-13-21 | D40035J | 6 | | | D42065P | 6 | | | 001-099 | |
| 5002Z | | | AC | | 0-0 | 34-13-21 | D40035J | 6 | | | D42065P | 6 | | | 115-199 | |
| 5003B | 24 | G2 | EC | | 34-0 | 22-32-11 | D40035J | 43 | | | D42063P | 2 | | | 001-099 | |
| 5003B | 24 | G2 | AN | | 34-0 | 22-32-11 | D40035J | 43 | | | D42063P | 2 | | | 115-199 | |
| 5003R | 24 | G2 | EC | | 0-0 | 22-32-11 | D40035J | 42 | | | D42063P | 1 | | | 001-099 | |
| 5003R | 24 | G2 | AN | | 0-0 | 22-32-11 | D40035J | 42 | | | D42063P | 1 | | | 115-199 | |
| 5003Z | | | EC | | 0-0 | 22-32-11 | D40035J | 44 | | | D42063P | 3 | | | 001-099 | |
| 5003Z | | | AN | | 0-0 | 22-32-11 | D40035J | 44 | | | D42063P | 3 | | | 115-199 | |
| 5004B | 24 | G2 | ED | | 40-0 | SPARE | D42055J | 14 | | | D42071P | 14 | | | 001-099 | |
| 5004R | 24 | G2 | ED | | 0-0 | SPARE | D42055J | 13 | | | D42071P | 13 | | | 001-099 | |
| 5004Z | | | ED | | 0-0 | SPARE | D42055J | 15 | | | D42071P | 15 | | | 001-099 | |
| 5005B | 24 | G2 | AH | | 41-0 | SPARE | D40035J | 17 | | | D42071P | 5 | | | 115-199 | |
| 5005R | 24 | G2 | AH | | 0-0 | SPARE | D40035J | 16 | | | D42071P | 4 | | | 115-199 | |
| 5005Z | | | AH | | 0-0 | SPARE | D40035J | 18 | | | D42071P | 6 | | | 115-199 | |
| 5006B | 24 | G2 | EF | | 34-0 | SPARE | D42055J | 11 | | | D42063P | 23 | | | 001-099 | |
| 5006B | 24 | G2 | AF | | 34-0 | SPARE | D42055J | 11 | | | D42063P | 23 | | | 115-199 | |
| 5006R | 24 | G2 | EF | | 0-0 | SPARE | D42055J | 10 | | | D42063P | 22 | | | 001-099 | |
| 5006R | 24 | G2 | AF | | 0-0 | SPARE | D42055J | 10 | | | D42063P | 22 | | | 115-199 | |
| 5006Z | | | EF | | 0-0 | SPARE | D42055J | 12 | | | D42063P | 24 | | | 001-099 | |
| 5006Z | | | AF | | 0-0 | SPARE | D42055J | 12 | | | D42063P | 24 | | | 115-199 | |
| 5008B | 24 | G2 | AT | | 34-0 | SPARE | D40035J | 11 | | | D42063P | 20 | | | 115-199 | |
| 5008R | 24 | G2 | AT | | 0-0 | SPARE | D40035J | 10 | | | D42063P | 19 | | | 115-199 | |
| 5008Z | | | AT | | 0-0 | SPARE | D40035J | 12 | | | D42063P | 21 | | | 115-199 | |
| 5010B | 24 | G2 | EJ | | 40-0 | SPARE | D40035J | 37 | | | D42069P | 13 | | | 001-099 | |
| 5010R | 24 | G2 | EJ | | 0-0 | SPARE | D40035J | 36 | | | D42069P | 12 | | | 001-099 | |
| 5010Z | | | EJ | | 0-0 | SPARE | D40035J | 38 | | | D42069P | 14 | | | 001-099 | |
| 5021B | 24 | G2 | AF | | 33-0 | 34-45-01 | D42055J | 43 | | | D42065P | 43 | | | 001-002 | |
| 5021B | 24 | G2 | AM | | 33-0 | 34-45-01 | D42055J | 34 | | | D42065P | 34 | | | 115-199 | |
| 5021R | 24 | G2 | AF | | 0-0 | 34-45-01 | D42055J | 42 | | | D42065P | 42 | | | 001-002 | |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2251 | 286N2251 | | | AP0003 TO E-E BAY - LEFT (continued) | | | | | | | | | | |
| 5021R | 24 | G2 | AM | 0-0 | 34-45-01 | D42055J | 33 | | | D42065P | 33 | | | 115-199 |
| 5021Z | | | AF | 0-0 | 34-45-01 | D42055J | | | AF | D42065P | 44 | | | 001-002 |
| 5021Z | | | AM | 0-0 | 34-45-01 | D42055J | | | AM | D42065P | 35 | | | 115-199 |
| 5022B | 24 | G2 | AG | 33-0 | 34-45-01 | D42055J | 49 | | | D42065P | 49 | | | 001-099 |
| 5022B | 24 | G2 | AG | 33-0 | 34-45-01 | D42055J | 40 | | | D42065P | 40 | | | 115-199 |
| 5022R | 24 | G2 | AG | 0-0 | 34-45-01 | D42055J | 48 | | | D42065P | 48 | | | 001-099 |
| 5022R | 24 | G2 | AG | 0-0 | 34-45-01 | D42055J | 39 | | | D42065P | 39 | | | 115-199 |
| 5022Z | | | AG | 0-0 | 34-45-01 | D42055J | | | AG | D42065P | 50 | | | 001-099 |
| 5022Z | | | AG | 0-0 | 34-45-01 | D42055J | | | AG | D42065P | 41 | | | 115-199 |
| FRAF | | | | 0-0 | 34-45-01 | D42055J | | | AF | D42055J | 44 | | | 001-002 |
| FRAG | | | | 0-0 | 34-45-01 | D42055J | | | AG | D42055J | 50 | | | 001-099 |
| FRAG | | | | 0-0 | 34-45-01 | D42055J | | | AG | D42055J | 41 | | | 115-199 |
| FRAM | | | | 0-0 | 34-45-01 | D42055J | | | AM | D42055J | 35 | | | 115-199 |
| W2253 | 286N2253 | | | AP0003 TO E-E BAY - RIGHT | | | | | | | | | | |
| 0001 | 24 | GK | | 31-0 | 34-12-62 | D40073J | 14 | | | D42089P | 1 | | | 001-099 |
| 0001 | 24 | GK | | 30-0 | 34-12-62 | D40073J | 14 | | | D42089P | 1 | | | 115-199 |
| 0002 | 24 | GK | | 30-0 | SPARE | D40073J | 37 | | | D42089P | 2 | | | 115-199 |
| 0003 | 22 | GA | | 28-0 | SPARE | D40099J | 3 | | | D42085P | 3 | | | ALL |
| 0004 | 22 | GA | | 31-0 | SPARE | D40099J | 4 | | | D42083P | 4 | | | 115-199 |
| 0005 | 22 | GA | | 28-0 | 22-14-21 | D40099J | 5 | | | D42085P | 5 | | | ALL |
| 0006 | 22 | GA | | 28-0 | 22-14-21 | D40099J | 6 | | | D42085P | 6 | | | ALL |
| 0007 | 22 | GA | | 28-0 | 22-14-21 | D40099J | 7 | | | D42085P | 7 | | | ALL |
| 0008 | 22 | GA | | 28-0 | 22-14-21 | D40099J | 8 | | | D42085P | 4 | | | ALL |
| 0009 | 24 | GK | | 28-0 | 34-22-27 | D40073J | 38 | | | D42085P | 42 | | | ALL |
| 0010 | 24 | GK | | 28-0 | 34-22-27 | D40073J | 39 | | | D42085P | 43 | | | ALL |
| 0011 | 24 | GK | | 28-0 | 34-22-27 | D40073J | 40 | | | D42085P | 44 | | | ALL |
| 0012 | 24 | GK | | 28-0 | 34-22-27 | D40073J | 41 | | | D42085P | 46 | | | ALL |
| 0013 | 24 | GK | | 32-0 | 34-46-11 | D40073J | 42 | | | D42083P | 13 | | | 001-099 |
| 0013 | 24 | GK | | 31-0 | 34-46-11 | D40073J | 42 | | | D42083P | 13 | | | 115-199 |
| 0014 | 24 | GK | | 32-0 | 34-46-11 | D40073J | 43 | | | D42083P | 14 | | | 001-099 |
| 0014 | 24 | GK | | 31-0 | 34-46-11 | D40073J | 43 | | | D42083P | 14 | | | 115-199 |
| 0015 | 22 | GA | | 28-0 | 22-41-13 | D40099J | 20 | | | D42085P | 41 | | | ALL |
| 0016 | 22 | GA | | 31-0 | SPARE | D40099J | 21 | | | D42083P | 16 | | | 115-199 |
| 0017 | 22 | GA | | 31-0 | SPARE | D40073J | 47 | | | D42083P | 17 | | | 115-199 |
| 0018 | 22 | GA | | 28-0 | 34-22-26 | D40073J | 7 | | | D42085P | 11 | | | 001-099 |
| 0018 | 24 | GK | | 28-0 | 34-22-26 | D40073J | 7 | | | D42085P | 11 | | | 115-199 |
| 0019 | 22 | GA | | 40-0 | 34-12-62 | D40073J | 18 | | | D42091P | 7 | | | 001-099 |
| 0019 | 22 | GA | | 41-0 | 34-12-62 | D40073J | 18 | | | D42091P | 7 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2253 | 286N2253 | | | AP0003 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | |
| 0020 | 22 | | GA | | 40-0 | SPARE | D40073J | 27 | | | D42091P | 14 | | | 001-099 |
| 0020 | 22 | | GA | | 41-0 | SPARE | D40073J | 27 | | | D42091P | 14 | | | 115-199 |
| 0021 | 22 | | GA | | 28-0 | SPARE | D40099J | 1 | | | D42085P | 15 | | | 115-199 |
| 0022 | 22 | | GA | | 28-0 | SPARE | D40099J | 2 | | | D42085P | 16 | | | 115-199 |
| 0023 | 24 | | GK | | 28-0 | 34-22-27 | D40073J | 31 | | | D42085P | 18 | | | ALL |
| 0024 | 22 | | GA | | 28-0 | 32-42-11 | D40073J | 32 | | | D42085P | 2 | | | ALL |
| 0025 | 24 | | GK | | 34-0 | 77-12-11 | D40099J | 25 | | | D42093P | 1 | | | 001-099 |
| 0025 | 22 | | GA | | 31-0 | SPARE | D40099J | 28 | | | D42083P | 25 | | | 115-199 |
| 0026 | 22 | | GA | | 31-0 | SPARE | D40099J | 29 | | | D42083P | 26 | | | 115-199 |
| 0027 | 22 | | GA | | 31-0 | SPARE | D40099J | 30 | | | D42083P | 27 | | | 115-199 |
| 0028 | 22 | | GA | | 31-0 | SPARE | D40099J | 31 | | | D42083P | 28 | | | 115-199 |
| 0029 | 24 | | GK | | 28-0 | 34-22-27 | D40073J | 33 | | | D42085P | 45 | | | ALL |
| 0030 | 22 | | CQ | | 37-0 | 34-46-11 | D40073J | 34 | | | D42083P | 4 | | | 002 |
| 0030 | 22 | | GA | | 31-0 | SPARE | D40073J | 34 | | | D42083P | 21 | | | 115-199 |
| 0031 | 24 | | PK | | 34-0 | 34-61-18 | D40099J | 47 | | | D42087P | 20 | | | 115-199 |
| 0032 | 22 | | GA | | 28-0 | 22-11-22 | D40631J | 10 | | | D42085P | 34 | | | ALL |
| 0033 | 22 | | GA | | 28-0 | 22-11-22 | D40631J | 11 | | | D42085P | 35 | | | ALL |
| 0034 | 22 | | GA | | 28-0 | SPARE | D40631J | 12 | | | D42085P | 36 | | | 001-099 |
| 0034 | 22 | | GA | | 28-0 | 22-11-22 | D40631J | 12 | | | D42085P | 36 | | | 115-199 |
| 0035 | 22 | | GA | | 28-0 | 22-11-22 | D40631J | 13 | | | D42085P | 37 | | | ALL |
| 0036 | 22 | | GA | | 31-0 | SPARE | D40631J | 14 | | | D42083P | 29 | | | 115-199 |
| 0037 | 22 | | GA | | 31-0 | SPARE | D40631J | 15 | | | D42083P | 30 | | | 115-199 |
| 0038 | 24 | | GK | | 40-0 | 34-55-21 | D40631J | 16 | | | D42091P | 21 | | | 001-099 |
| 0038 | 24 | | GK | | 42-0 | 34-55-21 | D40631J | 16 | | | D42091P | 33 | | | 115-199 |
| 0039 | 22 | | GA | | 28-0 | 34-51-21 | D40631J | 28 | | | D42087P | 7 | | | ALL |
| 0048 | 22 | | GA | | 28-2 | 34-12-62 | D41041J | 1 | | | D42085P | 48 | | | 001-099 |
| 0048 | 22 | | GA | | 27-0 | 34-12-62 | D41041J | 1 | | | D42085P | 48 | | | 115-199 |
| 0049 | 22 | | GA | | 28-2 | 34-12-62 | D41041J | 2 | | | D42085P | 49 | | | 001-099 |
| 0049 | 22 | | GA | | 27-0 | 34-12-62 | D41041J | 2 | | | D42085P | 49 | | | 115-199 |
| 0050 | 22 | | GA | | 36-0 | SPARE | D41041J | 3 | | | D42095P | 8 | | | 001-099 |
| 0050 | 22 | | GA | | 35-0 | SPARE | D41041J | 3 | | | D42095P | 8 | | | 115-199 |
| 0051 | 22 | | GA | | 36-0 | SPARE | D41041J | 4 | | | D42095P | 20 | | | 001-099 |
| 0051 | 22 | | GA | | 35-0 | SPARE | D41041J | 4 | | | D42095P | 20 | | | 115-199 |
| 0052 | 24 | | GK | | 36-0 | 27-51-11 | D41041J | 5 | | | D42095P | 10 | | | 001-099 |
| 0052 | 22 | | GA | | 35-0 | 27-51-11 | D41041J | 5 | | | D42095P | 10 | | | 115-199 |
| 0053 | 24 | | GK | | 36-0 | 27-51-11 | D41041J | 6 | | | D42095P | 9 | | | 001-099 |
| 0053 | 22 | | GA | | 35-0 | 27-51-11 | D41041J | 6 | | | D42095P | 9 | | | 115-199 |
| 0054 | 24 | | GK | | 36-0 | 27-51-11 | D41041J | 7 | | | D42095P | 1 | | | 001-099 |
| 0054 | 24 | | GK | | 35-0 | 27-51-11 | D41041J | 7 | | | D42095P | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2253 | | 286N2253 | | | | AP0003 TO E-E BAY - RIGHT (continued) | | | | | | | | | |
| 0055 | 24 | GK | | | 36-0 | 27-51-11 | D41041J | | 8 | | D42095P | | 2 | | 001-099 |
| 0055 | 24 | GK | | | 35-0 | 27-51-11 | D41041J | | 8 | | D42095P | | 2 | | 115-199 |
| 0056 | 24 | GK | | | 36-0 | 27-51-11 | D41041J | | 9 | | D42095P | | 3 | | 001-099 |
| 0056 | 24 | GK | | | 35-0 | 27-51-11 | D41041J | | 9 | | D42095P | | 3 | | 115-199 |
| 0057 | 24 | GK | | | 36-0 | 27-51-11 | D41041J | | 10 | | D42095P | | 4 | | 001-099 |
| 0057 | 24 | GK | | | 35-0 | 27-51-11 | D41041J | | 10 | | D42095P | | 4 | | 115-199 |
| 0058 | 24 | GK | | | 36-0 | 27-51-11 | D41041J | | 11 | | D42095P | | 5 | | 001-099 |
| 0058 | 24 | GK | | | 35-0 | 27-51-11 | D41041J | | 11 | | D42095P | | 5 | | 115-199 |
| 0059 | 24 | GK | | | 36-0 | 27-51-11 | D41041J | | 12 | | D42095P | | 6 | | 001-099 |
| 0059 | 24 | GK | | | 35-0 | 27-51-11 | D41041J | | 12 | | D42095P | | 6 | | 115-199 |
| 0060 | 24 | GK | | | 35-0 | 27-51-11 | D41041J | | 13 | | D42095P | | 7 | | 115-199 |
| 0061 | 24 | GK | | | 36-0 | 27-51-11 | D41041J | | 14 | | D42095P | | 19 | | 001-099 |
| 0061 | 24 | GK | | | 35-0 | 27-51-11 | D41041J | | 14 | | D42095P | | 19 | | 115-199 |
| 0064 | 22 | GA | | | 28-0 | 32-31-11 | D41041J | | 17 | | D42085P | | 24 | | 001-099 |
| 0064 | 22 | GA | | | 27-0 | 32-31-11 | D41041J | | 17 | | D42085P | | 24 | | 115-199 |
| 0065 | 24 | GK | | | 36-0 | 27-51-31 | D41041J | | 19 | | D42095P | | 14 | | 001-099 |
| 0065 | 22 | GA | | | 35-0 | 27-51-31 | D41041J | | 19 | | D42095P | | 14 | | 115-199 |
| 0066 | 22 | GA | | | 28-0 | 34-22-26 | D40073J | | 25 | | D42087P | | 24 | | ALL |
| 0067 | 22 | GA | | | 34-0 | 32-61-21 | D41041J | | 20 | | D42093P | | 7 | | ALL |
| 0069 | 22 | GA | | | 34-0 | 32-61-21 | D41041J | | 22 | | D42093P | | 9 | | ALL |
| 0070 | 24 | GK | | | 34-0 | 77-12-11 | D41041J | | 23 | | D42093P | | 1 | | 115-199 |
| 0071 | 22 | GA | | | 34-0 | SPARE | D41041J | | 24 | | D42093P | | 2 | | 115-199 |
| 0072 | 22 | GA | | | 34-0 | SPARE | D41041J | | 25 | | D42093P | | 3 | | 115-199 |
| 0074 | 22 | GA | | | 40-0 | 32-61-12 | D40099J | | 49 | | D42091P | | 3 | | 001-099 |
| 0074 | 22 | GA | | | 41-0 | 32-61-12 | D40099J | | 49 | | D42091P | | 3 | | 115-199 |
| 0075 | 24 | GK | | | 40-0 | 32-61-12 | D40099J | | 50 | | D42091P | | 1 | | 001-099 |
| 0075 | 22 | GA | | | 41-0 | 32-61-12 | D40099J | | 50 | | D42091P | | 1 | | 115-199 |
| 0076 | 24 | GK | | | 40-0 | 32-61-12 | D40099J | | 51 | | D42091P | | 27 | | 001-099 |
| 0076 | 24 | GK | | | 41-0 | 32-61-12 | D40099J | | 51 | | D42091P | | 27 | | 115-199 |
| 0077 | 22 | GA | | | 42-0 | SPARE | D40631J | | 42 | | D42091P | | 43 | | 115-199 |
| 0078 | 22 | GA | | | 42-0 | SPARE | D40631J | | 43 | | D42091P | | 44 | | 115-199 |
| 0079 | 22 | GA | | | 31-0 | SPARE | D40099J | | 18 | | D42083P | | 12 | | 115-199 |
| 0080 | 24 | GK | | | 32-0 | SPARE | D40099J | | 19 | | D42083P | | 15 | | 001-099 |
| 0080 | 22 | GA | | | 31-0 | SPARE | D40099J | | 19 | | D42083P | | 15 | | 115-199 |
| 0081 | 22 | GA | | | 31-0 | SPARE | D40099J | | 35 | | D42083P | | 18 | | 115-199 |
| 0082 | 22 | GA | | | 31-0 | SPARE | D40099J | | 36 | | D42083P | | 19 | | 115-199 |
| 0083 | 22 | GA | | | 40-0 | 32-61-12 | D40099J | | 48 | | D42091P | | 2 | | ALL |
| 0084 | 22 | GA | | | 30-0 | SPARE | D40073J | | 24 | | D42089P | | 17 | | 115-199 |
| 0085 | 22 | GA | | | 28-0 | 34-12-22 | D40631J | | 44 | | D42087P | | 8 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2253 | 286N2253 | | | AP0003 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | |
| 0086 | 22 | | GA | | 28-0 | 34-12-22 | D40631J | | 45 | | D42087P | | 9 | | 115-199 |
| 0087 | 22 | | GA | | 41-0 | 34-55-21 | D41041J | | 42 | | D42091P | | 21 | | 115-199 |
| 0088 | 24 | | GK | | 41-0 | 34-55-21 | D41041J | | 46 | | D42091P | | 25 | | 115-199 |
| 0089 | 24 | | GK | | 23-0 | 31-51-31 | D41041J | | 47 | | D42081P | | 2 | | ALL |
| 0090 | 24 | | GK | | 23-0 | SPARE | D41041J | | 49 | | D42081P | | 1 | | 115-199 |
| 0091 | 24 | | GK | | 23-0 | 31-51-21 | D41041J | | 48 | | D42081P | | 12 | | ALL |
| 0092 | 24 | | GK | | 32-0 | 34-25-11 | D42083P | | 5 | | D41041J | | 26 | | 001, 003-099 |
| 0092 | 24 | | GK | | 31-0 | 34-25-11 | D41041J | | 26 | | D42083P | | 5 | | 115-199 |
| 0093 | 22 | | GA | | 23-0 | SPARE | D40099J | | 37 | | D42081P | | 13 | | 115-199 |
| 0094 | 22 | | GA | | 23-0 | SPARE | D40099J | | 38 | | D42081P | | 14 | | 115-199 |
| 0095 | 22 | | GA | | 28-0 | SPARE | D40631J | | 46 | | D42087P | | 13 | | 115-199 |
| 0096 | 22 | | GA | | 162-0 | SPARE | D41041J | | 15 | | D42003P | | 9 | | 115-199 |
| 0097 | 22 | | GA | | 162-0 | SPARE | D41041J | | 16 | | D42003P | | 10 | | 115-199 |
| 0098 | 22 | | GA | | 162-0 | SPARE | D41041J | | 18 | | D42003P | | 11 | | 115-199 |
| 0104 | 22 | | GA | | 36-0 | 27-51-21 | D40099J | | 15 | | D42095P | | 15 | | ALL |
| 0105 | 22 | | GA | | 36-0 | 27-51-21 | D40099J | | 16 | | D42095P | | 16 | | ALL |
| 0106 | 22 | | GA | | 36-0 | 27-51-21 | D40099J | | 17 | | D42095P | | 17 | | ALL |
| 0107 | 22 | | PA | | 28-3 | 34-61-26 | D40073J | | 35 | | D42085P | | 1 | | 115-199 |
| 0108 | 22 | | PA | | 28-3 | 34-61-25 | D40073J | | 36 | | D42085P | | 17 | | 115-199 |
| 0125 | 22 | | CQ | | 37-0 | 34-22-28 | D40073J | | 51 | | D42083P | | 6 | | 002 |
| 2001B | 22 | | GB | AA | 28-0 | 34-12-21 | D40073J | | 23 | | D42085P | | 23 | | 001-099 |
| 2001B | 22 | | GB | AB | 28-0 | 34-12-21 | D40073J | | 23 | | D42085P | | 23 | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 34-12-21 | D40073J | | 22 | | D42085P | | 22 | | 001-099 |
| 2001R | 22 | | GB | AB | 0-0 | 34-12-21 | D40073J | | 22 | | D42085P | | 22 | | 115-199 |
| 2006B | 22 | | GB | AF | 41-0 | 34-51-21 | D40631J | | 27 | | D42091P | | 28 | | 001-099 |
| 2006B | 22 | | GB | AW | 162-0 | 34-51-21 | D40631J | | 27 | | D42003P | | 5 | | 115-199 |
| 2006R | 22 | | GB | AF | 0-0 | 34-51-21 | D40631J | | 26 | | D42091P | | 26 | | 001-099 |
| 2006R | 22 | | GB | AW | 0-0 | 34-51-21 | D40631J | | 26 | | D42003P | | 4 | | 115-199 |
| 2501B | 24 | | G2 | BA | 28-0 | SPARE | D40073J | | 45 | | D42085P | | 51 | | 001-099 |
| 2501R | 24 | | G2 | BA | 0-0 | SPARE | D40073J | | 44 | | D42085P | | 50 | | 001-099 |
| 2501Z | | | | BA | 0-0 | SPARE | D40073J | | 46 | | D42085P | | 52 | | 001-099 |
| 2502B | 24 | | G2 | AL | 28-0 | SPARE | D40073J | | 49 | | D42085P | | 13 | | 115-199 |
| 2502R | 24 | | G2 | AL | 0-0 | SPARE | D40073J | | 48 | | D42085P | | 12 | | 115-199 |
| 2502Z | | | | AL | 0-0 | SPARE | D40073J | | 50 | | D42085P | | 14 | | 115-199 |
| 2503B | 24 | | G2 | AN | 41-0 | SPARE | D40073J | | 54 | | D42091P | | 9 | | 115-199 |
| 2503R | 24 | | G2 | AN | 0-0 | SPARE | D40073J | | 53 | | D42091P | | 8 | | 115-199 |
| 2503Z | | | | AN | 0-0 | SPARE | D40073J | | 55 | | D42091P | | 10 | | 115-199 |
| 2504B | 24 | | G2 | BC | 34-0 | SPARE | D41041J | | 54 | | D42093P | | 5 | | 001-099 |
| 2504B | 24 | | G2 | BU | 34-0 | 77-12-11 | D41041J | | 54 | | D42093P | | 5 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | | |
|------------|-------------|----|-------|---------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2253 | 286N2253 | | | AP0003 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | | |
| 2504R | 24 | | G2 | BC | 0-0 | SPARE | D41041J | 53 | | | | D42093P | 4 | | | 001-099 |
| 2504R | 24 | | G2 | BU | 0-0 | 77-12-11 | D41041J | 53 | | | | D42093P | 4 | | | 115-199 |
| 2504Z | | | | BC | 0-0 | SPARE | D41041J | 55 | | | | D42093P | 6 | | | 001-099 |
| 2504Z | | | | BU | 0-0 | 77-12-11 | D41041J | 55 | | | | D42093P | 6 | | | 115-199 |
| 2505B | 24 | | G2 | AQ | 30-0 | SPARE | D40099J | 23 | | | | D42089P | 10 | | | 115-199 |
| 2505R | 24 | | G2 | AQ | 0-0 | SPARE | D40099J | 22 | | | | D42089P | 9 | | | 115-199 |
| 2505Z | | | | AQ | 0-0 | SPARE | D40099J | 24 | | | | D42089P | 11 | | | 115-199 |
| 2506B | 24 | | G2 | AR | 30-0 | SPARE | D40099J | 26 | | | | D42089P | 13 | | | 115-199 |
| 2506R | 24 | | G2 | AR | 0-0 | SPARE | D40099J | 25 | | | | D42089P | 12 | | | 115-199 |
| 2506Z | | | | AR | 0-0 | SPARE | D40099J | 27 | | | | D42089P | 14 | | | 115-199 |
| 2509B | 24 | | G2 | BG | 35-0 | SPARE | D41041J | 34 | | | | D42095P | 29 | | | 115-199 |
| 2509R | 24 | | G2 | BG | 0-0 | SPARE | D41041J | 33 | | | | D42095P | 28 | | | 115-199 |
| 2509Z | | | | BG | 0-0 | SPARE | D41041J | 35 | | | | D42095P | 30 | | | 115-199 |
| 2510B | 24 | | G2 | BI | 42-0 | SPARE | D40631J | 40 | | | | D42091P | 41 | | | 115-199 |
| 2510R | 24 | | G2 | BI | 0-0 | SPARE | D40631J | 39 | | | | D42091P | 40 | | | 115-199 |
| 2510Z | | | | BI | 0-0 | SPARE | D40631J | 41 | | | | D42091P | 42 | | | 115-199 |
| 2511B | 24 | | G2 | BE | 28-0 | SPARE | D40631J | 37 | | | | D42085P | 32 | | | 115-199 |
| 2511R | 24 | | G2 | BE | 0-0 | SPARE | D40631J | 36 | | | | D42085P | 31 | | | 115-199 |
| 2511Z | | | | BE | 0-0 | SPARE | D40631J | 38 | | | | D42085P | 33 | | | 115-199 |
| 2512B | 24 | | G2 | BL | 34-0 | 77-12-11 | D40099J | 53 | | | | D42093P | 14 | | | 001-099 |
| 2512R | 24 | | G2 | BL | 0-0 | 77-12-11 | D40099J | 52 | | | | D42093P | 13 | | | 001-099 |
| 2512Z | | | | BL | 0-0 | 77-12-11 | D40099J | 54 | | | | D42093P | 15 | | | 001-099 |
| 3001B | 24 | | GM | CA | 28-0 | 34-12-21 | D40073J | 20 | | | | D42085P | 20 | | | 001-099 |
| 3001B | 24 | | GM | AA | 28-0 | 34-12-21 | D40073J | 20 | | | | D42085P | 20 | | | 115-199 |
| 3001R | 24 | | GM | CA | 0-0 | 34-12-21 | D40073J | 19 | | | | D42085P | 19 | | | 001-099 |
| 3001R | 24 | | GM | AA | 0-0 | 34-12-21 | D40073J | 19 | | | | D42085P | 19 | | | 115-199 |
| 3001Y | 24 | | GM | CA | 0-0 | 34-12-21 | D40073J | 21 | | | | D42085P | 21 | | | 001-099 |
| 3001Y | 24 | | GM | AA | 0-0 | 34-12-21 | D40073J | 21 | | | | D42085P | 21 | | | 115-199 |
| 3501B | 24 | | G3 | DA | 40-0 | 23-51-12 | D40631J | 33 | | | | D42091P | 23 | | | 001-099 |
| 3501B | 24 | | G3 | BD | 42-0 | 23-51-12 | D40631J | 33 | | | | D42091P | 36 | | | 115-199 |
| 3501R | 24 | | G3 | DA | 0-0 | 23-51-12 | D40631J | 32 | | | | D42091P | 22 | | | 001-099 |
| 3501R | 24 | | G3 | BD | 0-0 | 23-51-12 | D40631J | 32 | | | | D42091P | 35 | | | 115-199 |
| 3501Y | 24 | | G3 | DA | 0-0 | 23-51-12 | D40631J | 34 | | | | D42091P | 24 | | | 001-099 |
| 3501Y | 24 | | G3 | BD | 0-0 | 23-51-12 | D40631J | 34 | | | | D42091P | 37 | | | 115-199 |
| 3501Z | | | | DA | 0-0 | 23-51-12 | D40631J | 35 | | | | D42091P | 25 | | | 001-099 |
| 3501Z | | | | BD | 0-0 | 23-51-12 | D40631J | 35 | | | | D42091P | 38 | | | 115-199 |
| 4501G | 22 | | DU | DM | 34-0 | 77-21-11 | D41041J | 52 | | | | D42093P | 12 | | | 001-099 |
| 4501G | 20 | | DU | BT | 34-0 | 77-21-11 | D41041J | 52 | TC | | | D42093P | 12 | TC | | 115-199 |
| 4501W | 22 | | DU | DM | 0-0 | 77-21-11 | D41041J | 51 | | | | D42093P | 11 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|---------------------------------------|-------------|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2253 | 286N2253 | | | AP0003 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | | |
| 4501W | 20 | | DU | BT | 0-0 | 77-21-11 | | D41041J | 51 | TD | | D42093P | 11 | TD | | 115-199 |
| 4501Z | | | | DM | 0-0 | 77-21-11 | | D41041J | 50 | | | D42093P | 10 | | | 001-099 |
| 4501Z | | | | BT | 0-0 | 77-21-11 | | D41041J | 50 | | | D42093P | 10 | | | 115-199 |
| 5001B | 24 | G2 | | EA | 28-0 | 34-13-21 | | D40073J | 3 | | | D42087P | 3 | | | 001-099 |
| 5001B | 24 | G2 | | AC | 28-0 | 34-13-21 | | D40073J | 3 | | | D42087P | 3 | | | 115-199 |
| 5001R | 24 | G2 | | EA | 0-0 | 34-13-21 | | D40073J | 2 | | | D42087P | 2 | | | 001-099 |
| 5001R | 24 | G2 | | AC | 0-0 | 34-13-21 | | D40073J | 2 | | | D42087P | 2 | | | 115-199 |
| 5001Z | | | | EA | 0-0 | 34-13-21 | | D40073J | 1 | | | D42087P | 1 | | | 001-099 |
| 5001Z | | | | AC | 0-0 | 34-13-21 | | D40073J | 1 | | | D42087P | 1 | | | 115-199 |
| 5002B | 24 | G2 | | EB | 28-0 | 34-22-91 | | D40073J | 5 | | | D42085P | 54 | | | 001-099 |
| 5002R | 24 | G2 | | EB | 0-0 | 34-22-91 | | D40073J | 4 | | | D42085P | 53 | | | 001-099 |
| 5002Z | | | | EB | 0-0 | 34-22-91 | | D40073J | 6 | | | D42085P | 55 | | | 001-099 |
| 5003B | 24 | G2 | | EC | 28-0 | 34-22-91 | | D40073J | 9 | | | D42085P | 9 | | | 001-099 |
| 5003B | 24 | G2 | | AE | 28-0 | SPARE | | D40073J | 9 | | | D42085P | 9 | | | 115-199 |
| 5003R | 24 | G2 | | EC | 0-0 | 34-22-91 | | D40073J | 8 | | | D42085P | 8 | | | 001-099 |
| 5003R | 24 | G2 | | AE | 0-0 | SPARE | | D40073J | 8 | | | D42085P | 8 | | | 115-199 |
| 5003Z | | | | EC | 0-0 | 34-22-91 | | D40073J | 10 | | | D42085P | 10 | | | 001-099 |
| 5003Z | | | | AE | 0-0 | SPARE | | D40073J | 10 | | | D42085P | 10 | | | 115-199 |
| 5004B | 24 | G2 | | ED | 31-0 | 34-22-92 | | D40073J | 12 | | | D42089P | 4 | | | 001-099 |
| 5004B | 24 | G2 | | AG | 30-0 | 34-22-92 | | D40073J | 12 | | | D42089P | 4 | | | 115-199 |
| 5004R | 24 | G2 | | ED | 0-0 | 34-22-92 | | D40073J | 11 | | | D42089P | 3 | | | 001-099 |
| 5004R | 24 | G2 | | AG | 0-0 | 34-22-92 | | D40073J | 11 | | | D42089P | 3 | | | 115-199 |
| 5004Z | | | | ED | 0-0 | 34-22-92 | | D40073J | 13 | | | D42089P | 5 | | | 001-099 |
| 5004Z | | | | AG | 0-0 | 34-22-92 | | D40073J | 13 | | | D42089P | 5 | | | 115-199 |
| 5005B | 24 | G2 | | EE | 23-0 | 22-14-21 | | D40099J | 10 | | | D42081P | 10 | | | 001-099 |
| 5005B | 24 | G2 | | AH | 23-0 | 22-14-21 | | D40099J | 10 | | | D42081P | 10 | | | 115-199 |
| 5005R | 24 | G2 | | EE | 0-0 | 22-14-21 | | D40099J | 9 | | | D42081P | 9 | | | 001-099 |
| 5005R | 24 | G2 | | AH | 0-0 | 22-14-21 | | D40099J | 9 | | | D42081P | 9 | | | 115-199 |
| 5005Z | | | | EE | 0-0 | 22-14-21 | | D40099J | 11 | | | D42081P | 11 | | | 001-099 |
| 5005Z | | | | AH | 0-0 | 22-14-21 | | D40099J | 11 | | | D42081P | 11 | | | 115-199 |
| 5006B | 24 | G2 | | EF | 40-0 | SPARE | | D40073J | 16 | | | D42091P | 16 | | | 001-099 |
| 5006R | 24 | G2 | | EF | 0-0 | SPARE | | D40073J | 15 | | | D42091P | 15 | | | 001-099 |
| 5006Z | | | | EF | 0-0 | SPARE | | D40073J | 17 | | | D42091P | 17 | | | 001-099 |
| 5007B | 24 | G2 | | EG | 28-0 | 22-12-21 | | D40631J | 2 | | | D42085P | 26 | | | 001-099 |
| 5007B | 24 | G2 | | BA | 28-0 | 22-12-21 | | D40631J | 2 | | | D42085P | 26 | | | 115-199 |
| 5007R | 24 | G2 | | EG | 0-0 | 22-12-21 | | D40631J | 1 | | | D42085P | 25 | | | 001-099 |
| 5007R | 24 | G2 | | BA | 0-0 | 22-12-21 | | D40631J | 1 | | | D42085P | 25 | | | 115-199 |
| 5007Z | | | | EG | 0-0 | 22-12-21 | | D40631J | 3 | | | D42085P | 27 | | | 001-099 |
| 5007Z | | | | BA | 0-0 | 22-12-21 | | D40631J | 3 | | | D42085P | 27 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2253 | 286N2253 | | | AP0003 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | |
| 5008B | 24 | | G2 | EH | 28-0 | 22-13-21 | D40631J | | | 5 | | D42085P | 29 | | 001-099 |
| 5008B | 24 | | G2 | BC | 28-0 | 22-13-21 | D40631J | | | 5 | | D42085P | 29 | | 115-199 |
| 5008R | 24 | | G2 | EH | 0-0 | 22-13-21 | D40631J | | | 4 | | D42085P | 28 | | 001-099 |
| 5008R | 24 | | G2 | BC | 0-0 | 22-13-21 | D40631J | | | 4 | | D42085P | 28 | | 115-199 |
| 5008Z | | | | EH | 0-0 | 22-13-21 | D40631J | | | 6 | | D42085P | 30 | | 001-099 |
| 5008Z | | | | BC | 0-0 | 22-13-21 | D40631J | | | 6 | | D42085P | 30 | | 115-199 |
| 5009B | 24 | | G2 | EI | 32-0 | 22-14-21 | D40631J | | | 8 | | D42083P | 10 | | 001-099 |
| 5009B | 24 | | G2 | BB | 31-0 | 22-14-21 | D40631J | | | 8 | | D42083P | 10 | | 115-199 |
| 5009R | 24 | | G2 | EI | 0-0 | 22-14-21 | D40631J | | | 7 | | D42083P | 9 | | 001-099 |
| 5009R | 24 | | G2 | BB | 0-0 | 22-14-21 | D40631J | | | 7 | | D42083P | 9 | | 115-199 |
| 5009Z | | | | EI | 0-0 | 22-14-21 | D40631J | | | 9 | | D42083P | 11 | | 001-099 |
| 5009Z | | | | BB | 0-0 | 22-14-21 | D40631J | | | 9 | | D42083P | 11 | | 115-199 |
| 5010B | 24 | | G2 | EJ | 40-0 | 34-55-21 | D40631J | | | 18 | | D42091P | 19 | | 001-099 |
| 5010B | 24 | | G2 | AT | 42-0 | 34-55-21 | D40631J | | | 18 | | D42091P | 19 | | 115-199 |
| 5010R | 24 | | G2 | EJ | 0-0 | 34-55-21 | D40631J | | | 17 | | D42091P | 18 | | 001-099 |
| 5010R | 24 | | G2 | AT | 0-0 | 34-55-21 | D40631J | | | 17 | | D42091P | 18 | | 115-199 |
| 5010Z | | | | EJ | 0-0 | 34-55-21 | D40631J | | | 19 | | D42091P | 20 | | 001-099 |
| 5010Z | | | | AT | 0-0 | 34-55-21 | D40631J | | | 19 | | D42091P | 20 | | 115-199 |
| 5011B | 24 | | G2 | EK | 28-0 | 34-51-21 | D40631J | | | 21 | | D42087P | 22 | | 001-099 |
| 5011B | 24 | | G2 | AU | 28-0 | 34-51-21 | D40631J | | | 21 | | D42087P | 22 | | 115-199 |
| 5011R | 24 | | G2 | EK | 0-0 | 34-51-21 | D40631J | | | 20 | | D42087P | 21 | | 001-099 |
| 5011R | 24 | | G2 | AU | 0-0 | 34-51-21 | D40631J | | | 20 | | D42087P | 21 | | 115-199 |
| 5011Z | | | | EK | 0-0 | 34-51-21 | D40631J | | | 22 | | D42087P | 23 | | 001-099 |
| 5011Z | | | | AU | 0-0 | 34-51-21 | D40631J | | | 22 | | D42087P | 23 | | 115-199 |
| 5012B | 24 | | G2 | EL | 28-0 | 34-51-21 | D40631J | | | 24 | | D42087P | 5 | | 001-099 |
| 5012B | 24 | | G2 | AV | 28-0 | 34-51-21 | D40631J | | | 24 | | D42087P | 5 | | 115-199 |
| 5012R | 24 | | G2 | EL | 0-0 | 34-51-21 | D40631J | | | 23 | | D42087P | 4 | | 001-099 |
| 5012R | 24 | | G2 | AV | 0-0 | 34-51-21 | D40631J | | | 23 | | D42087P | 4 | | 115-199 |
| 5012Z | | | | EL | 0-0 | 34-51-21 | D40631J | | | 25 | | D42087P | 6 | | 001-099 |
| 5012Z | | | | AV | 0-0 | 34-51-21 | D40631J | | | 25 | | D42087P | 6 | | 115-199 |
| 5013B | 24 | | G2 | EM | 41-0 | 34-51-21 | D40631J | | | 30 | | D42091P | 30 | | 001-099 |
| 5013B | 24 | | G2 | AX | 162-0 | 34-51-21 | D40631J | | | 30 | | D42003P | 2 | | 115-199 |
| 5013R | 24 | | G2 | EM | 0-0 | 34-51-21 | D40631J | | | 29 | | D42091P | 29 | | 001-099 |
| 5013R | 24 | | G2 | AX | 0-0 | 34-51-21 | D40631J | | | 29 | | D42003P | 1 | | 115-199 |
| 5013Z | | | | EM | 0-0 | 34-51-21 | D40631J | | | 31 | | D42091P | 31 | | 001-099 |
| 5013Z | | | | AX | 0-0 | 34-51-21 | D40631J | | | 31 | | D42003P | 3 | | 115-199 |
| 5014B | 24 | | G2 | EN | 28-0 | 31-25-11 | D40099J | | | 33 | | D42085P | 39 | | 001-099 |
| 5014B | 24 | | G2 | AY | 28-0 | 31-25-11 | D40099J | | | 33 | | D42085P | 39 | | 115-199 |
| 5014R | 24 | | G2 | EN | 0-0 | 31-25-11 | D40099J | | | 32 | | D42085P | 38 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|---------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2253 | 286N2253 | | | AP0003 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | | |
| 5014R | 24 | | G2 | AY | 0-0 | 31-25-11 | D40099J | 32 | | | D42085P | 38 | | | 115-199 | |
| 5014Z | | | | EN | 0-0 | 31-25-11 | D40099J | 34 | | | D42085P | 40 | | | 001-099 | |
| 5014Z | | | | AY | 0-0 | 31-25-11 | D40099J | 34 | | | D42085P | 40 | | | 115-199 | |
| 5015B | 24 | | G2 | EO | 23-0 | SPARE | D40099J | 13 | | | D42081P | 4 | | | 001-099 | |
| 5015B | 24 | | G2 | BJ | 23-0 | SPARE | D40099J | 13 | | | D42081P | 4 | | | 115-199 | |
| 5015R | 24 | | G2 | EO | 0-0 | SPARE | D40099J | 12 | | | D42081P | 3 | | | 001-099 | |
| 5015R | 24 | | G2 | BJ | 0-0 | SPARE | D40099J | 12 | | | D42081P | 3 | | | 115-199 | |
| 5015Z | | | | EO | 0-0 | SPARE | D40099J | 14 | | | D42081P | 5 | | | 001-099 | |
| 5015Z | | | | BJ | 0-0 | SPARE | D40099J | 14 | | | D42081P | 5 | | | 115-199 | |
| 5016B | 24 | | G2 | EP | 28-0 | SPARE | D40073J | 28 | | | D42087P | 10 | | | 001-099 | |
| 5016B | 24 | | G2 | BK | 28-0 | SPARE | D40073J | 28 | | | D42087P | 10 | | | 115-199 | |
| 5016R | 24 | | G2 | EP | 0-0 | SPARE | D40073J | 29 | | | D42087P | 11 | | | 001-099 | |
| 5016R | 24 | | G2 | BK | 0-0 | SPARE | D40073J | 29 | | | D42087P | 11 | | | 115-199 | |
| 5016Z | | | | EP | 0-0 | SPARE | D40073J | 30 | | | D42087P | 12 | | | 001-099 | |
| 5016Z | | | | BK | 0-0 | SPARE | D40073J | 30 | | | D42087P | 12 | | | 115-199 | |
| 5017B | 24 | | G2 | EQ | 40-0 | 34-22-91 | D41041J | 37 | | | D42091P | 9 | | | 001-099 | |
| 5017B | 24 | | G2 | BL | 162-0 | 34-22-93 | D41041J | 37 | | | D42003P | 7 | | | 115-199 | |
| 5017R | 24 | | G2 | EQ | 0-0 | 34-22-91 | D41041J | 36 | | | D42091P | 8 | | | 001-099 | |
| 5017R | 24 | | G2 | BL | 0-0 | 34-22-93 | D41041J | 36 | | | D42003P | 6 | | | 115-199 | |
| 5017Z | | | | EQ | 0-0 | 34-22-91 | D41041J | 38 | | | D42091P | 10 | | | 001-099 | |
| 5017Z | | | | BL | 0-0 | 34-22-93 | D41041J | 38 | | | D42003P | 8 | | | 115-199 | |
| 5018B | 24 | | G2 | BM | 27-0 | 34-22-93 | D41041J | 40 | | | D42087P | 15 | | | 115-199 | |
| 5018R | 24 | | G2 | BM | 0-0 | 34-22-93 | D41041J | 39 | | | D42087P | 14 | | | 115-199 | |
| 5018Z | | | | BM | 0-0 | 34-22-93 | D41041J | 41 | | | D42087P | 16 | | | 115-199 | |
| 5019B | 24 | | G2 | BO | 27-0 | 34-55-21 | D41041J | 44 | | | D42085P | 54 | | | 115-199 | |
| 5019R | 24 | | G2 | BO | 0-0 | 34-55-21 | D41041J | 43 | | | D42085P | 53 | | | 115-199 | |
| 5019Z | | | | BO | 0-0 | 34-55-21 | D41041J | 45 | | | D42085P | 55 | | | 115-199 | |
| 5020B | 24 | | G2 | ET | 36-0 | SPARE | D41041J | 27 | | | D42095P | 11 | | | 001-099 | |
| 5020B | 24 | | G2 | BP | 27-0 | 34-22-18 | D41041J | 28 | | | D42085P | 51 | | | 115-199 | |
| 5020R | 24 | | G2 | ET | 0-0 | SPARE | D41041J | 28 | | | D42095P | 12 | | | 001-099 | |
| 5020R | 24 | | G2 | BP | 0-0 | 34-22-18 | D41041J | 27 | | | D42085P | 50 | | | 115-199 | |
| 5020Z | | | | ET | 0-0 | SPARE | D41041J | 29 | | | D42095P | 13 | | | 001-099 | |
| 5020Z | | | | BP | 0-0 | 34-22-18 | D41041J | 29 | | | D42085P | 52 | | | 115-199 | |
| 5021B | 24 | | G2 | BQ | 162-0 | SPARE | D41041J | 31 | | | D42003P | 12 | | | 115-199 | |
| 5021R | 24 | | G2 | BQ | 0-0 | SPARE | D41041J | 30 | | | D42003P | 13 | | | 115-199 | |
| 5021Z | | | | BQ | 0-0 | SPARE | D41041J | 32 | | | D42003P | 14 | | | 115-199 | |
| 5024B | 24 | | G2 | EX | 36-0 | SPARE | D40099J | 40 | | | D42095P | 27 | | | 001-099 | |
| 5024R | 24 | | G2 | EX | 0-0 | SPARE | D40099J | 39 | | | D42095P | 26 | | | 001-099 | |
| 5024Z | | | | EX | 0-0 | SPARE | D40099J | 41 | | | D42095P | 25 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | | To | | | | | Effectivity |
|------------|-------------|----|-------|---------------------------------------|---------|----------|---------|-------|------|------|---------|-------|------|------|--------------|-------------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2253 | 286N2253 | | | AP0003 TO E-E BAY - RIGHT (continued) | | | | | | | | | | | | |
| 5025B | 24 | G2 | EY | | 36-0 | SPARE | D41041J | 34 | | | D42095P | 29 | | | 001-099 | |
| 5025R | 24 | G2 | EY | | 0-0 | SPARE | D41041J | 33 | | | D42095P | 28 | | | 001-099 | |
| 5025Z | | | EY | | 0-0 | SPARE | D41041J | 35 | | | D42095P | 30 | | | 001-099 | |
| 5026B | 24 | G2 | EZ | | 24-0 | SPARE | D42083P | 2 | | | D42095P | 33 | | | 001-099 | |
| 5026R | 24 | G2 | EZ | | 0-0 | SPARE | D42083P | 1 | | | D42095P | 32 | | | 001-099 | |
| 5026Z | | | EZ | | 0-0 | SPARE | D42083P | 3 | | | D42095P | 34 | | | 001-099 | |
| 5027B | 24 | G2 | FA | | 32-0 | SPARE | D40099J | 30 | | | D42083P | 7 | | | 001-099 | |
| 5027R | 24 | G2 | FA | | 0-0 | SPARE | D40099J | 29 | | | D42083P | 6 | | | 001, 003-099 | |
| 5027R | 24 | G2 | FA | | 0-0 | SPARE | D40099J | 29 | | | D42083P | CAP | Y | | 002 | |
| 5027Z | | | FA | | 0-0 | SPARE | D40099J | 31 | | | D42083P | 8 | | | 001-099 | |
| 5028B | 24 | G2 | FB | | 31-0 | SPARE | D40099J | 23 | | | D42089P | 10 | | | 001-099 | |
| 5028R | 24 | G2 | FB | | 0-0 | SPARE | D40099J | 22 | | | D42089P | 9 | | | 001-099 | |
| 5028Z | | | FB | | 0-0 | SPARE | D40099J | 24 | | | D42089P | 11 | | | 001-099 | |
| W2255 | 286N2255 | | | ILS CONTROL PANEL (L2) | | | | | | | | | | | | |
| 0001 | 20 | GA | | | 6-0 | 34-31-11 | D00269 | 7 | | | GD00082 | ST.. | 2 | | ALL | |
| 0002 | 24 | GK | | | 34-0 | 34-31-11 | D00269 | 5 | | | D42105P | 5 | | | ALL | |
| 0003 | 24 | GK | | | 34-0 | 34-31-11 | D00269 | 11 | | | D42105P | 11 | | | ALL | |
| 2001B | 22 | GB | AA | | 34-0 | 34-31-11 | D00269 | 8 | | | D42105P | 8 | | | ALL | |
| 2001R | 22 | GB | AA | | 0-0 | 34-31-11 | D00269 | 9 | | | D42105P | 9 | | | ALL | |
| 5001B | 24 | G2 | AB | | 34-0 | 34-31-11 | D00269 | 13 | | | D42105P | 14 | | | ALL | |
| 5001R | 24 | G2 | AB | | 0-0 | 34-31-11 | D00269 | 14 | | | D42105P | 13 | | | ALL | |
| 5001Z | | | AB | | 0-0 | 34-31-11 | D00269 | 12 | | | D42105P | 12 | | | ALL | |
| W2256 | 286N2256 | | | P6 TO P36 LEFT AC | | | | | | | | | | | | |
| 0001 | 14 | GA | | | 35-0 | 24-53-11 | D40866P | 1 | | | D41746P | 14 | | | ALL | |
| 0002 | 16 | GA | | | 19-0 | 21-25-11 | D41746P | 18 | | | D40910P | 4 | | | ALL | |
| 0003 | 20 | GA | | | 35-0 | 24-53-11 | D40866P | 3 | | | D41746P | 3 | | | ALL | |
| 0005 | 24 | GK | | | 20-0 | 30-31-11 | D40866P | 5 | | | D41416P | 4 | | | 001-099 | |
| 0005 | 20 | GA | | | 21-0 | 30-31-11 | D40866P | 5 | | | D41416P | 4 | | | 115-199 | |
| 0006 | 20 | GA | | | 31-0 | SPARE | D40866P | 18 | | | D40910P | 12 | | | 115-199 | |
| 0007 | 24 | GK | | | 21-0 | 30-31-11 | D40866P | 7 | | | D41416P | 18 | | | 001-099 | |
| 0007 | 20 | GA | | | 31-0 | 30-31-11 | D40866P | 7 | | | D40910P | 7 | | | 115-199 | |
| 0008 | 20 | GA | | | 31-0 | SPARE | D40866P | 19 | | | D40910P | 13 | | | 115-199 | |
| 0009 | 20 | GA | | | 31-0 | 29-11-22 | D40866P | 32 | | | D40910P | 32 | | | 001-099 | |
| 0009 | 20 | GA | | | 31-0 | 29-11-22 | D40866P | 20 | | | D40910P | 14 | | | 115-199 | |
| 0011 | 20 | GA | | | 31-0 | SPARE | D40866P | 22 | | | D40910P | 16 | | | 115-199 | |
| 0012 | 20 | GA | | | 31-0 | 29-11-31 | D40866P | 23 | | | D40910P | 17 | | | ALL | |
| 0021 | 22 | GA | | | 31-0 | 30-32-11 | D40866P | 21 | | | D40910P | 21 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2256 | 286N2256 | | | | P6 TO P36 LEFT AC (continued) | | | | | | | | | | | | |
| 0021 | 22 | | GA | | 32-0 | 30-32-11 | D40866P | 21 | | | D40910P | 21 | | | 115-199 | | |
| 0022 | 18 | | GA | | 23-0 | 33-42-21 | D41416P | 13 | | | D40910P | 8 | | | 001-099 | | |
| 0022 | 18 | | GA | | 24-0 | 33-42-21 | D41416P | 13 | | | D40910P | 8 | | | 115-199 | | |
| 0026 | 20 | | GA | | 21-0 | SPARE | D40866P | 27 | | | D41416P | 14 | | | 115-199 | | |
| 0027 | 20 | | GA | | 24-0 | SPARE | D41416P | 15 | | | D40910P | 18 | | | 115-199 | | |
| 0028 | 20 | | GA | | 23-0 | 33-42-31 | D41416P | 16 | | | D40910P | 19 | | | 001-099 | | |
| 0028 | 20 | | GA | | 24-0 | SPARE | D41416P | 16 | | | D40910P | 19 | | | 115-199 | | |
| 0030 | 20 | | GA | | 35-0 | SPARE | D40866P | 29 | | | D41746P | 2 | | | ALL | | |
| 0032 | 20 | | GA | | 35-0 | SPARE | D40866P | 31 | | | D41746P | 4 | | | ALL | | |
| 0033 | 20 | | GA | | 19-0 | SPARE | D41746P | 5 | | | D40910P | 20 | | | 115-199 | | |
| 0037 | 20 | | GA | | 19-0 | SPARE | D41746P | 9 | | | D40910P | 25 | | | 115-199 | | |
| 0038 | 20 | | GA | | 20-0 | 21-25-11 | D41746P | 10 | | | D40910P | 26 | | | 001-099 | | |
| 0038 | 20 | | GA | | 19-0 | 21-25-11 | D41746P | 10 | | | D40910P | 26 | | | 115-199 | | |
| 0040 | 22 | | GA | | 30-0 | 21-58-15 | D40866P | 24 | | | D40910P | 22 | | | 001-099 | | |
| 0040 | 22 | | GA | | 31-0 | 21-58-15 | D40866P | 24 | | | D40910P | 22 | | | 115-199 | | |
| 0041 | 22 | | GA | | 30-0 | 21-58-15 | D40866P | 28 | | | D40910P | 23 | | | 001-099 | | |
| 0041 | 22 | | GA | | 31-0 | 21-58-15 | D40866P | 28 | | | D40910P | 23 | | | 115-199 | | |
| 0042 | 22 | | GA | | 30-0 | 21-58-15 | D40866P | 30 | | | D40910P | 24 | | | 001-099 | | |
| 0042 | 22 | | GA | | 31-0 | 21-58-15 | D40866P | 30 | | | D40910P | 24 | | | 115-199 | | |
| 0601 | 20 | | GA | | 21-0 | SPARE | D40866P | 9 | | | D41416P | 6 | | | 115-199 | | |
| 0602 | 24 | | GK | | 21-0 | 21-25-11 | D40910P | 3 | | | D41746P | 11 | | | 001-099 | | |
| 0602 | 24 | | GK | | 20-0 | 21-25-11 | D40910P | 3 | | | D41746P | 11 | | | 115-199 | | |
| 0603 | 20 | | GA | | 31-0 | SPARE | D40866P | 11 | | | D40910P | 5 | | | 115-199 | | |
| 0604 | 20 | | GA | | 24-0 | SPARE | D41416P | 5 | | | D40910P | 9 | | | 115-199 | | |
| 0606 | 20 | | GA | | 19-0 | SPARE | D41746P | 19 | | | D40910P | 11 | | | 115-199 | | |
| 0607 | 20 | | GA | | 19-0 | SPARE | D41746P | 12 | | | D40910P | 27 | | | 115-199 | | |
| 0608 | 20 | | GA | | 19-0 | SPARE | D41746P | 13 | | | D40910P | 28 | | | 115-199 | | |
| 0609 | 20 | | GA | | 19-0 | SPARE | D41746P | 16 | | | D40910P | 29 | | | 115-199 | | |
| 0610 | 20 | | GA | | 19-0 | SPARE | D41746P | 15 | | | D40910P | 30 | | | 115-199 | | |
| 0612 | 20 | | GA | | 35-0 | SPARE | D40866P | 25 | | | D41746P | 17 | | | 115-199 | | |
| 0613 | 14 | | GA | | 31-0 | SPARE | D40866P | 8 | | | D40910P | 1 | | | 115-199 | | |
| 3002B | 16 | | GC | AA | 20-0 | 28-22-11 | D40866P | 2 | | | D41416P | 9 | | | 001-099 | | |
| 3002B | 16 | | GC | AA | 21-0 | 28-22-11 | D40866P | 2 | | | D41416P | 9 | | | 115-199 | | |
| 3002R | 16 | | GC | AA | 0-0 | 28-22-11 | D40866P | 4 | | | D41416P | 7 | | | ALL | | |
| 3002Y | 16 | | GC | AA | 0-0 | 28-22-11 | D40866P | 6 | | | D41416P | 8 | | | ALL | | |
| 3012B | 18 | | GC | AB | 20-0 | 28-22-11 | D40866P | 12 | 18 | | D41416P | 3 | | | 001-099 | | |
| 3012B | 18 | | GC | AB | 21-0 | 28-22-11 | D40866P | 12 | 18 | | D41416P | 3 | | | 115-199 | | |
| 3012R | 18 | | GC | AB | 0-0 | 28-22-11 | D40866P | 13 | 18 | | D41416P | 1 | | | ALL | | |
| 3012Y | 18 | | GC | AB | 0-0 | 28-22-11 | D40866P | 14 | 18 | | D41416P | 2 | | | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2256 | 286N2256 | | | P6 TO P36 LEFT AC (continued) | | | | | | | | | | | |
| 3015B | 18 | | GC | AC | 20-0 | 28-22-11 | D40866P | 15 | 18 | | D41416P | 12 | | | 001-099 |
| 3015B | 18 | | GC | AC | 21-0 | 28-22-11 | D40866P | 15 | 18 | | D41416P | 12 | | | 115-199 |
| 3015R | 18 | | GC | AC | 0-0 | 28-22-11 | D40866P | 16 | 18 | | D41416P | 10 | | | ALL |
| 3015Y | 18 | | GC | AC | 0-0 | 28-22-11 | D40866P | 17 | 18 | | D41416P | 11 | | | ALL |
| W2257 | 286N2257 | | | ILS CONTROL PANEL (R2) | | | | | | | | | | | |
| 0001 | 20 | | GA | | 6-0 | 34-31-21 | D00273 | 7 | | | GD01650 | ST.. | 2 | | 001-099 |
| 0001 | 20 | | GA | | 7-0 | 34-31-21 | D00273 | 7 | | | GD01650 | ST.. | 2 | | 115-199 |
| 0002 | 24 | | GK | | 36-0 | 34-31-21 | D00273 | 5 | | | D42107P | 5 | | | 001-099 |
| 0002 | 24 | | GK | | 35-0 | 34-31-21 | D00273 | 5 | | | D42107P | 5 | | | 115-199 |
| 0003 | 24 | | GK | | 36-0 | 34-31-21 | D00273 | 11 | | | D42107P | 11 | | | 001-099 |
| 0003 | 24 | | GK | | 35-0 | 34-31-21 | D00273 | 11 | | | D42107P | 11 | | | 115-199 |
| 2001B | 22 | | GB | AA | 36-0 | 34-31-21 | D00273 | 8 | | | D42107P | 8 | | | 001-099 |
| 2001B | 22 | | GB | AA | 35-0 | 34-31-21 | D00273 | 8 | | | D42107P | 8 | | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 34-31-21 | D00273 | 9 | | | D42107P | 9 | | | ALL |
| 5001B | 24 | | G2 | AB | 36-0 | 34-31-21 | D00273 | 13 | | | D42107P | 3 | | | 001-099 |
| 5001B | 24 | | G2 | AB | 35-0 | 34-31-21 | D00273 | 13 | | | D42107P | 13 | | | 115-199 |
| 5001R | 24 | | G2 | AB | 0-0 | 34-31-21 | D00273 | 14 | | | D42107P | 4 | | | 001-099 |
| 5001R | 24 | | G2 | AB | 0-0 | 34-31-21 | D00273 | 14 | | | D42107P | 14 | | | 115-199 |
| 5001Z | | | | AB | 0-0 | 34-31-21 | D00273 | 12 | | | D42107P | 2 | | | 001-099 |
| 5001Z | | | | AB | 0-0 | 34-31-21 | D00273 | 12 | | | D42107P | 12 | | | 115-199 |
| W2258 | 286N2258 | | | P6 TO P37, RIGHT AC | | | | | | | | | | | |
| 0001 | 16 | | GA | | 27-0 | SPARE | D40868P | 1 | | | D40912P | 1 | | | 001-099 |
| 0001 | 20 | | GA | | 27-0 | SPARE | D40868P | 1 | | | D40912P | 1 | | | 115-199 |
| 0003 | 20 | | GA | | 27-0 | SPARE | D40868P | 3 | | | D40912P | 3 | | | 115-199 |
| 0005 | 24 | | GK | | 27-0 | 30-31-12 | D40868P | 5 | | | D40912P | 5 | | | 001-099 |
| 0005 | 20 | | GA | | 27-0 | 30-31-12 | D40868P | 5 | | | D40912P | 5 | | | 115-199 |
| 0007 | 20 | | GA | | 27-0 | SPARE | D40868P | 7 | | | D40912P | 7 | | | 115-199 |
| 0009 | 20 | | GA | | 27-0 | SPARE | D40868P | 9 | | | D40912P | 9 | | | 115-199 |
| 0011 | 24 | | GK | | 27-0 | 30-31-12 | D40868P | 11 | | | D40912P | 11 | | | 001-099 |
| 0011 | 20 | | GA | | 27-0 | 30-31-12 | D40868P | 11 | | | D40912P | 11 | | | 115-199 |
| 0021 | 22 | | GA | | 27-0 | 30-32-11 | D40868P | 21 | | | D40912P | 21 | | | ALL |
| 0022 | 20 | | GA | | 27-0 | 24-31-11 | D40868P | 22 | | | D40912P | 22 | | | ALL |
| 0023 | 20 | | GA | | 27-0 | 24-31-11 | D40868P | 23 | | | D40912P | 23 | | | ALL |
| 0024 | 20 | | GA | | 27-0 | 24-31-11 | D40868P | 24 | | | D40912P | 24 | | | ALL |
| 0025 | 20 | | GA | | 27-0 | SPARE | D40868P | 25 | | | D40912P | 25 | | | 115-199 |
| 0028 | 18 | | GA | | 27-0 | 38-15-11 | D40868P | 28 | | | D40912P | 28 | | | ALL |
| 0029 | 18 | | GA | | 27-0 | 38-15-11 | D40868P | 29 | | | D40912P | 29 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2258 | 286N2258 | | | P6 TO P37, RIGHT AC (continued) | | | | | | | | | | | |
| 0030 | 18 | | GA | | 27-0 | 38-15-11 | D40868P | | 30 | | D40912P | | 30 | | ALL |
| 0601 | 20 | | GA | | 27-0 | SPARE | D40868P | | 2 | | D40912P | | 2 | | ALL |
| 0602 | 18 | | GA | | 27-0 | 24-51-25 | D40912P | | 43 | | D40868P | | 43 | | 001-099 |
| 0602 | 18 | | GA | | 27-0 | 24-51-25 | D40868P | | 43 | | D40912P | | 43 | | 115-199 |
| 0603 | 16 | | GA | | 27-0 | SPARE | D40868P | | 42 | | D40912P | | 42 | | 115-199 |
| 0604 | 16 | | GA | | 27-0 | 21-58-13 | D40868P | | 41 | | D40912P | | 41 | | 001-099 |
| 0604 | 16 | | GA | | 27-0 | SPARE | D40868P | | 41 | | D40912P | | 41 | | 115-199 |
| 0605 | 16 | | GA | | 27-0 | 21-58-13 | D40868P | | 40 | | D40912P | | 40 | | 001-099 |
| 0605 | 16 | | GA | | 27-0 | SPARE | D40868P | | 40 | | D40912P | | 40 | | 115-199 |
| 0606 | 16 | | GA | | 27-0 | 21-58-13 | D40868P | | 27 | | D40912P | | 27 | | 001-099 |
| 0606 | 16 | | GA | | 27-0 | SPARE | D40868P | | 27 | | D40912P | | 27 | | 115-199 |
| 0607 | 20 | | GA | | 27-0 | SPARE | D40868P | | 13 | | D40912P | | 13 | | 115-199 |
| 0609 | 18 | | GA | | 27-0 | SPARE | D40868P | | 15 | | D40912P | | 15 | | ALL |
| 0611 | 20 | | GA | | 27-0 | SPARE | D40868P | | 16 | | D40912P | | 16 | | 115-199 |
| 0612 | 20 | | GA | | 27-0 | SPARE | D40868P | | 17 | | D40912P | | 17 | | 115-199 |
| 0613 | 20 | | GA | | 27-0 | SPARE | D40868P | | 18 | | D40912P | | 18 | | 115-199 |
| 0614 | 20 | | GA | | 27-0 | SPARE | D40868P | | 19 | | D40912P | | 19 | | 115-199 |
| 0615 | 20 | | GA | | 27-0 | SPARE | D40868P | | 20 | | D40912P | | 20 | | 115-199 |
| 0616 | 20 | | GA | | 27-0 | SPARE | D40868P | | 4 | | D40912P | | 4 | | 115-199 |
| 0617 | 20 | | GA | | 27-0 | SPARE | D40868P | | 6 | | D40912P | | 6 | | 115-199 |
| 0618 | 20 | | GA | | 27-0 | SPARE | D40868P | | 8 | | D40912P | | 8 | | 115-199 |
| 0619 | 20 | | GA | | 27-0 | SPARE | D40868P | | 10 | | D40912P | | 10 | | 115-199 |
| 3002B | 16 | | GC | AA | 27-0 | 28-22-11 | D40868P | | 31 | | D40912P | | 31 | | ALL |
| 3002R | 16 | | GC | AA | 0-0 | 28-22-11 | D40868P | | 32 | | D40912P | | 32 | | ALL |
| 3002Y | 16 | | GC | AA | 0-0 | 28-22-11 | D40868P | | 33 | | D40912P | | 33 | | ALL |
| 3012B | 18 | | GC | AB | 27-0 | 28-22-11 | D40868P | | 39 | | D40912P | | 39 | | ALL |
| 3012R | 18 | | GC | AB | 0-0 | 28-22-11 | D40868P | | 37 | | D40912P | | 37 | | ALL |
| 3012Y | 18 | | GC | AB | 0-0 | 28-22-11 | D40868P | | 38 | | D40912P | | 38 | | ALL |
| 3015B | 18 | | GC | AC | 27-0 | 28-22-11 | D40868P | | 36 | | D40912P | | 36 | | ALL |
| 3015R | 18 | | GC | AC | 0-0 | 28-22-11 | D40868P | | 34 | | D40912P | | 34 | | ALL |
| 3015Y | 18 | | GC | AC | 0-0 | 28-22-11 | D40868P | | 35 | | D40912P | | 35 | | ALL |
| W2259 | 286N2259 | | | ILS CONTROL PANEL (C2) | | | | | | | | | | | |
| 0001 | 20 | | GA | | 6-0 | 34-31-31 | D00271 | | 7 | | GD00082 | ST.. | 2 | | 001-099 |
| 0001 | 20 | | GA | | 5-0 | 34-31-31 | D00271 | | 7 | | GD00082 | ST.. | 2 | | 115-199 |
| 0002 | 24 | | GK | | 31-0 | 34-31-31 | D00271 | | 5 | | D42109P | | 5 | | ALL |
| 0003 | 24 | | GK | | 31-0 | 34-31-31 | D00271 | | 11 | | D42109P | | 11 | | ALL |
| 0004 | 20 | | GA | | 6-0 | 33-13-52 | D00271 | | 1 | | TB0159Z | 12 | BJ | | 001-099 |
| 0004 | 20 | | GA | | 5-0 | 33-13-52 | D00271 | | 1 | | TB0159Z | 12 | BJ | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2259 | 286N2259 | | | ILS CONTROL PANEL (C2) (continued) | | | | | | | | | | | |
| 0005 | 20 | | GA | | 6-0 | 33-13-52 | D00271 | | 2 | | GD00082 | AC.. | 2 | | 001-099 |
| 0005 | 20 | | GA | | 5-0 | 33-13-52 | D00271 | | 2 | | GD00082 | AC.. | 2 | | 115-199 |
| 2001B | 22 | | GB | AA | 31-0 | 34-31-31 | D00271 | | 8 | | D42109P | | 8 | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 34-31-31 | D00271 | | 9 | | D42109P | | 9 | | ALL |
| 5001B | 24 | | G2 | AB | 31-0 | 34-31-31 | D00271 | | 13 | | D42109P | | 13 | | ALL |
| 5001R | 24 | | G2 | AB | 0-0 | 34-31-31 | D00271 | | 14 | | D42109P | | 14 | | ALL |
| 5001Z | | | | AB | 0-0 | 34-31-31 | D00271 | | 12 | | D42109P | | 12 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2250

Page 18 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2260 | 286N2260 | | | P6 TO P36 - BATTERY BUS | | | | | | | | | | | |
| 0001 | 18 | | GA | | 20-0 | 28-21-11 | D40870P | 4 | 18 | | D41420P | 10 | 18 | | 001-099 |
| 0002 | 22 | | GA | | 33-0 | 24-25-11 | D40870P | 23 | | | D40914P | 6 | | | 001-002 |
| 0002 | 22 | | GA | | 33-0 | 24-25-11 | D40870P | 14 | | | D40914P | 6 | | | 003-099 |
| 0002 | 22 | | GA | | 32-0 | 24-25-11 | D40870P | 23 | | | D40914P | 6 | | | 115-199 |
| 0003 | 20 | | GA | | 33-0 | 24-31-11 | D40870P | 1 | | | D40914P | 8 | | | 003-099 |
| 0011 | 16 | | GA | | 20-0 | 28-21-11 | D40870P | 11 | 16 | | D41420P | 2 | 16 | | 001-099 |
| 0011 | 16 | | GA | | 22-0 | 28-21-11 | D40870P | 11 | 16 | | D41420P | 2 | 16 | | 115-199 |
| 0013 | 16 | | GA | | 20-0 | 28-21-11 | D40870P | 13 | 16 | | D41420P | 1 | 16 | | 001-099 |
| 0013 | 16 | | GA | | 22-0 | 28-21-11 | D40870P | 13 | 16 | | D41420P | 1 | 16 | | 115-199 |
| 0015 | 22 | | GA | | 30-0 | 21-58-11 | D40870P | 15 | | | D40914P | 15 | | | 001-099 |
| 0015 | 22 | | GA | | 32-0 | 21-58-11 | D40870P | 15 | | | D40914P | 15 | | | 115-199 |
| 0016 | 16 | | GA | | 20-0 | 28-21-11 | D40870P | 16 | 16 | | D41420P | 3 | 16 | | 001-002 |
| 0016 | 16 | | GA | | 20-0 | 28-21-11 | D40870P | 12 | 16 | | D41420P | 3 | 16 | | 003-099 |
| 0016 | 16 | | GA | | 22-0 | 28-21-11 | D40870P | 16 | 16 | | D41420P | 3 | 16 | | 115-199 |
| 0020 | 20 | | GA | | 20-0 | 28-22-21 | D40870P | 20 | | | TB0058X | C008 | BJ | | 001-002 |
| 0020 | 20 | | GA | | 20-0 | 28-22-21 | D40870P | 3 | | | TB0058X | C008 | BJ | | 003-099 |
| 0020 | 20 | | GA | | 21-0 | 28-22-21 | D40870P | 20 | | | TB0058X | C008 | BJ | | 115-199 |
| 0021 | 22 | | GA | | 20-0 | 76-11-12 | D40870P | 21 | | | TB0058X | B001 | BJ | | 001-002 |
| 0021 | 22 | | GA | | 20-0 | 76-11-12 | D40870P | 2 | | | TB0058X | B001 | BJ | | 003-099 |
| 0021 | 22 | | GA | | 21-0 | 76-11-12 | D40870P | 21 | | | TB0058X | B001 | BJ | | 115-199 |
| 0024 | 10 | | HA | | 40-0 | 32-35-11 | K10369 | A1 | E | | TB5011 | 9 | E | | 001-099 |
| 0024 | 10 | | HA | | 39-0 | 32-35-11 | K10369 | A1 | E | | TB5011 | 9 | E | | 115-199 |
| 0028 | 12 | | HA | | 37-0 | 29-21-31 | TB5011 | 10 | E | | SP01526 | | 9 | | 001-099 |
| 0028 | 12 | | HA | | 31-0 | 29-21-31 | TB5011 | 10 | E | | SP01526 | | 9 | | 115-199 |
| 0055 | 20 | | GA | | 30-0 | SPARE | D40870P | 5 | | | D40914P | 5 | | | 001-099 |
| 0055 | 20 | | GA | | 32-0 | 26-22-21 | D40870P | 5 | | | D40914P | 5 | | | 115-199 |
| 0603 | 22 | | GA | | 22-0 | SPARE | D40870P | 8 | | | D41420P | 4 | | | 115-199 |
| 0604 | 22 | | GA | | 22-0 | SPARE | D40870P | 9 | | | D41420P | 5 | | | 115-199 |
| 0605 | 22 | | GA | | 22-0 | SPARE | D40870P | 10 | | | D41420P | 6 | | | 115-199 |
| 0606 | 22 | | GA | | 22-0 | SPARE | D40870P | 12 | | | D41420P | 7 | | | 115-199 |
| 0607 | 22 | | GA | | 22-0 | SPARE | D40870P | 14 | | | D41420P | 8 | | | 115-199 |
| 0608 | 22 | | GA | | 30-0 | 32-44-11 | D40870P | 17 | | | D40914P | 1 | | | 001-002 |
| 0608 | 22 | | GA | | 30-0 | 32-44-11 | D40870P | 10 | | | D40914P | 1 | | | 003-099 |
| 0608 | 22 | | GA | | 32-0 | 32-44-11 | D40870P | 17 | | | D40914P | 1 | | | 115-199 |
| 0609 | 22 | | GA | | 32-0 | SPARE | D40870P | 18 | | | D40914P | 2 | | | 115-199 |
| 0610 | 20 | | GA | | 30-0 | 29-11-31 | D40870P | 19 | | | D40914P | 3 | | | 001-002 |
| 0610 | 20 | | GA | | 30-0 | 29-11-31 | D40870P | 9 | | | D40914P | 3 | | | 003-099 |
| 0610 | 20 | | GA | | 32-0 | 29-11-31 | D40870P | 19 | | | D40914P | 3 | | | 115-199 |
| 0611 | 20 | | GA | | 32-0 | SPARE | D40870P | 22 | | | D40914P | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2260

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2260 | 286N2260 | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| 0614 | 20 | | GA | | 32-0 | SPARE | D40870P | 6 | | | D40914P | 9 | | | 115-199 |
| 0615 | 20 | | GA | | 22-0 | SPARE | D40870P | 7 | | | D41420P | 9 | | | 115-199 |
| W2261 | 286N2261 | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-31-11 | D00191 | = C1 | | | D42121P | = C1 | | | ALL |
| 001CX | | 94 | | AA | 33-0 | 34-31-11 | D00191 | = A1 | | | D42121P | = A1 | | | ALL |
| W2263 | 286N2263 | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-31-21 | D00195 | = C1 | | | D42123P | = C1 | | | ALL |
| 001CX | | 94 | | AA | 30-0 | 34-31-21 | D00195 | = A1 | | | D42123P | = A1 | | | ALL |
| W2265 | 286N2265 | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-31-11 | D40715J | = C1 | | | D42125P | = C1 | | | ALL |
| 001CX | | 94 | | AA | 33-0 | 34-31-11 | D40715J | = A1 | | | D42125P | = A1 | | | ALL |
| W2267 | 286N2267 | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-31-21 | D40717J | = C1 | | | D42127P | = C1 | | | ALL |
| 001CX | | 94 | | AA | 29-0 | 34-31-21 | D40717J | = A1 | | | D42127P | = A1 | | | ALL |
| W2269 | 286N2269 | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 4-0 | 34-12-11 | D00469 | 12 | | | GD00084 | ST.. | E | | 001-099 |
| 0001 | 20 | | GA | | 5-0 | 34-12-11 | D00469 | 12 | | | GD00084 | ST.. | E | | 115-199 |
| 0007 | 22 | | GA | | 29-0 | 30-32-11 | D42129P | 7 | | | D00295 | 8 | | | ALL |
| 0009 | 22 | | GA | | 4-0 | 30-32-11 | D00295 | 9 | | | GD02450 | AC.. | E | | ALL |
| 0010 | 22 | | GA | | 29-0 | 30-32-11 | D00295 | 10 | | | D42129P | 6 | | | ALL |
| 0012 | 20 | | GA | | 4-0 | 30-32-11 | D00295 | 12 | | | GD00084 | ST.. | E | | 001-099 |
| 0012 | 20 | | GA | | 5-0 | 30-32-11 | D00295 | 12 | | | GD00084 | ST.. | E | | 115-199 |
| 2001B | 22 | | GB | AA | 29-0 | 34-12-11 | D00295 | 2 | | | D42129P | 2 | | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 34-12-11 | D00295 | 1 | | | D42129P | 1 | | | ALL |
| 2002B | 22 | | GB | AC | 29-0 | 34-12-11 | D00469 | 2 | | | D42129P | 9 | | | ALL |
| 2002R | 22 | | GB | AC | 0-0 | 34-12-11 | D00469 | 1 | | | D42129P | 8 | | | ALL |
| 3001B | 24 | | GM | AB | 29-0 | 34-12-11 | D00295 | 4 | | | D42129P | 4 | | | ALL |
| 3001R | 24 | | GM | AB | 0-0 | 34-12-11 | D00295 | 3 | | | D42129P | 3 | | | ALL |
| 3001Y | 24 | | GM | AB | 0-0 | 34-12-11 | D00295 | 5 | | | D42129P | 5 | | | ALL |
| 3002B | 24 | | GM | AD | 29-0 | 34-12-11 | D00469 | 4 | | | D42129P | 10 | | | ALL |
| 3002R | 24 | | GM | AD | 0-0 | 34-12-11 | D00469 | 3 | | | D42129P | 11 | | | ALL |
| 3002Y | 24 | | GM | AD | 0-0 | 34-12-11 | D00469 | 5 | | | D42129P | 12 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2260

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|-------------|--------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W2271 | 286N2271 | | | | TOTAL AIR TEMP TS5001 TO E-E BAY | | | | | | | | | | | |
| 0001 | 20 | | HA | | 9-0 | 30-33-11 | D02774 | | 1 | | | D42133P | 1 | | | 001-099 |
| 0001 | 20 | | HA | | 10-0 | 30-33-11 | D02774 | | 1 | | | D42133P | 1 | | | 115-199 |
| 0006 | 20 | | HA | | 9-0 | 30-33-11 | D02774 | | 6 | | | D42133P | 6 | | | 001-099 |
| 0006 | 20 | | HA | | 10-0 | 30-33-11 | D02774 | | 6 | | | D42133P | 6 | | | 115-199 |
| 0007 | 20 | | HA | | 2-0 | 34-12-21 | D02774 | | 7 | | | GD00262 | ST.. | E | | ALL |
| 2501B | 20 | | HF | AA | 11-0 | 34-12-11 | D02774 | | 4 | | | D42135P | 4 | | | ALL |
| 2501R | 20 | | HF | AA | 0-0 | 34-12-11 | D02774 | | 3 | | | D42135P | 3 | | | ALL |
| 2501Z | | | | AA | 0-0 | 34-12-11 | D02774 | | DED | | | D42135P | 2 | | | ALL |
| 2502B | 20 | | HF | AB | 9-0 | 34-12-21 | D02774 | | 5 | | | D42133P | 3 | | | ALL |
| 2502R | 20 | | HF | AB | 0-0 | 34-12-21 | D02774 | | 2 | | | D42133P | 2 | | | ALL |
| 2502Z | | | | AB | 0-0 | 34-12-21 | D02774 | | DED | | | D42133P | 4 | | | ALL |
| W2273 | 286N2273 | | | | ILS LOC ANTENNA - CENTER | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-31-31 | D00199 | | = C1 | | | D42137P | = C1 | | | ALL |
| 001CX | | 94 | | AA | 32-0 | 34-31-31 | D00199 | | = A1 | | | D42137P | = A1 | | | ALL |
| W2275 | 286N2275 | | | | ILS AND G/S ATENNA-CENTER | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-31-31 | D40719J | | = C1 | | | D42139P | = C1 | | | ALL |
| 001CX | | 94 | | AA | 31-0 | 34-31-31 | D40719J | | = A1 | | | D42139P | = A1 | | | ALL |
| W2277 | 286N2277 | | | | RIGHT ANGLE OF ATTACK SENSOR TO E-E BAY (TS13) | | | | | | | | | | | |
| 0001 | 20 | | GA | | 3-0 | 34-12-21 | D00467 | | 12 | | | GD00083 | ST.. | E | | ALL |
| 0007 | 22 | | GA | | 31-0 | 30-32-11 | D42143P | | 7 | | | D00293 | 8 | | | ALL |
| 0009 | 22 | | GA | | 3-0 | 30-32-11 | D00293 | | 9 | | | GD02459 | AC.. | E | | ALL |
| 0010 | 22 | | GA | | 31-0 | 30-32-11 | D00293 | | 10 | | | D42143P | 6 | | | ALL |
| 0012 | 20 | | GA | | 3-0 | 30-32-11 | D00293 | | 12 | | | GD00083 | ST.. | E | | ALL |
| 2001B | 22 | | GB | AA | 31-0 | 34-12-21 | D00467 | | 2 | | | D42143P | 8 | | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 34-12-21 | D00467 | | 1 | | | D42143P | 9 | | | ALL |
| 2002B | 22 | | GB | AC | 31-0 | 34-12-21 | D00293 | | 2 | | | D42143P | 2 | | | ALL |
| 2002R | 22 | | GB | AC | 0-0 | 34-12-21 | D00293 | | 1 | | | D42143P | 1 | | | ALL |
| 3001B | 24 | | GM | AB | 31-0 | 34-12-21 | D00467 | | 4 | | | D42143P | 10 | | | ALL |
| 3001R | 24 | | GM | AB | 0-0 | 34-12-21 | D00467 | | 3 | | | D42143P | 11 | | | ALL |
| 3001Y | 24 | | GM | AB | 0-0 | 34-12-21 | D00467 | | 5 | | | D42143P | 12 | | | ALL |
| 3002B | 24 | | GM | AD | 31-0 | 34-12-21 | D00293 | | 4 | | | D42143P | 4 | | | ALL |
| 3002R | 24 | | GM | AD | 0-0 | 34-12-21 | D00293 | | 3 | | | D42143P | 3 | | | ALL |
| 3002Y | 24 | | GM | AD | 0-0 | 34-12-21 | D00293 | | 5 | | | D42143P | 5 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2270

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2293 | 286N2293 | | | OBS INTERPHONE-P8 TO OBS INTERPHONE PNL | | | | | | | | | | | |
| 0001 | 20 | | GA | | 10-0 | 33-13-11 | D00459 | | 1 | | SP01056 | | 9 | | 001-099 |
| 0001 | 20 | | GA | | 12-0 | 33-13-11 | D00459 | | 1 | | SP01056 | | 9 | | 115-199 |
| 0002 | 20 | | GA | | 5-0 | 33-13-11 | D00459 | | 2 | | GD00343 | AC.. | 2 | | ALL |
| 0003 | 22 | | GA | | 19-0 | 23-51-41 | D00459 | | 3 | | TB0058Y | A005 | BJ | | 001-099 |
| 0004 | 20 | | GA | | 5-0 | 23-51-41 | D00459 | | 4 | | GD00343 | DC.. | 2 | | ALL |
| 0005 | 24 | | GK | | 1-0 | 23-51-41 | D00459 | | 23 | | D00459 | | 24 | | ALL |
| 0006 | 20 | | GA | | 5-0 | 23-51-41 | D00459 | | | AA | GD00343 | ST.. | 2 | | ALL |
| 0007 | 22 | | GA | | 19-0 | 23-51-41 | D00459 | | 3 | | TB0113Y | C017 | BJ | | 115-199 |
| 2001B | 24 | | GL | AA | 3-0 | 23-51-41 | D00459 | | 13 | | D40171 | | 1 | VY | 001-099 |
| 2001B | 24 | | GL | AA | 3-0 | 23-51-41 | D00459 | | 13 | | D00521 | | 2 | | 115-199 |
| 2001R | 24 | | GL | AA | 0-0 | 23-51-41 | D00459 | | 14 | | D40173 | | 1 | VR | 001-099 |
| 2001R | 24 | | GL | AA | 0-0 | 23-51-41 | D00459 | | 14 | | D00521 | | 1 | | 115-199 |
| 2501B | 24 | | G2 | AB | 3-0 | 23-51-41 | D00459 | | 15 | | D40177 | | 1 | VG | 001-099 |
| 2501B | 24 | | G2 | AB | 3-0 | 23-51-41 | D00459 | | 15 | | D00521 | | 4 | | 115-199 |
| 2501R | 24 | | G2 | AB | 0-0 | 23-51-41 | D00459 | | 16 | | D40175 | | 1 | VS | 001-099 |
| 2501R | 24 | | G2 | AB | 0-0 | 23-51-41 | D00459 | | 16 | | D00521 | | 3 | | 115-199 |
| 2501Z | | | | AB | 0-0 | 23-51-41 | D00459 | | | AA | D40175 | DED | | | 001-099 |
| 2501Z | | | | AB | 0-0 | 23-51-41 | D00459 | | | AA | D00521 | DED | | | 115-199 |
| 2502B | 24 | | G2 | AC | 4-0 | 23-51-41 | D00459 | | 8 | | D00527 | | 2 | | ALL |
| 2502R | 24 | | G2 | AC | 0-0 | 23-51-41 | D00459 | | 9 | | D00527 | | 1 | | ALL |
| 2502Z | | | | AC | 0-0 | 23-51-41 | D00459 | | | AA | D00527 | | 3 | | ALL |
| 2503B | 24 | | G2 | AE | 19-0 | 23-51-41 | TB0158X | D004 | BJ | | SM00004 | | 9 | | 001-099 |
| 2503R | 24 | | G2 | AE | 0-0 | 23-51-41 | TB0158X | C004 | BJ | | SM00006 | | 9 | | 001-099 |
| 2503Z | | | | AE | 0-0 | 23-51-41 | TB0158X | A004 | BJ | | SM00REF | | 4 | AB | 001-099 |
| 3501B | 24 | | G3 | AD | 2-0 | 23-51-41 | D00459 | | 12 | | SM00004 | | 9 | | 001-099 |
| 3501B | 24 | | G3 | AD | 3-0 | 23-51-41 | D00459 | | 12 | | SM00004 | | 9 | | 115-199 |
| 3501R | 24 | | G3 | AD | 0-0 | 23-51-41 | D00459 | | 10 | | SM00005 | | 9 | | ALL |
| 3501Y | 24 | | G3 | AD | 0-0 | 23-51-41 | D00459 | | 11 | | SM00006 | | 9 | | ALL |
| 3501Z | | | | AD | 0-0 | 23-51-41 | D00459 | | | AA | SM00REF | | 4 | AB | 001-099 |
| 3501Z | | | | AD | 0-0 | 23-51-41 | D00459 | | | AA | SM00004 | DED | | | 115-199 |
| A-AE | | | | | 0-0 | 23-51-41 | D00523 | | BLU | | SM00004 | | 9 | | ALL |
| A-AF | | | | | 0-0 | 23-51-41 | D00523 | | BLK | | SM00006 | | 9 | | ALL |
| A-AG | | | | | 0-0 | 23-51-41 | D00525 | | RED | | SM00005 | | 9 | | ALL |
| A-AH | | | | | 0-0 | 23-51-41 | D00525 | | BLU | | SM00004 | | 9 | | ALL |
| A-AI | | | | | 0-0 | 23-51-41 | D00525 | | BLK | | SM00006 | | 9 | | ALL |
| W2295 | 286N2295 | | | F/O INTERPHONE-P8 TO F/O AUX PNL(P14) | | | | | | | | | | | |
| 0001 | 16 | | GA | | 7-0 | 33-13-51 | D00451 | | 1 | 16 | TB0158F | A010 | 2 | | 001-099 |
| 0001 | 16 | | GA | | 5-0 | 33-13-51 | D00451 | | 1 | 16 | TB0158F | A010 | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2290

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2295 | 286N2295 | | | | F/O INTERPHONE-P8 TO F/O AUX PNL(P14) (continued) | | | | | | | | | | | | |
| 0002 | 16 | | GA | | 6-0 | 33-13-51 | D00451 | | 2 | 16 | | GD00742 | AC.. | 2 | | 001-099 | |
| 0002 | 16 | | GA | | 4-0 | 33-13-51 | D00451 | | 2 | 16 | | GD00742 | AC.. | 2 | | 115-199 | |
| 0003 | 22 | | GA | | 7-0 | 23-51-21 | D00451 | | 3 | | | TB0058Y | A005 | BJ | | 001-099 | |
| 0003 | 22 | | GA | | 5-0 | 23-51-21 | D00451 | | 3 | | | TB0058Y | A005 | BJ | | 115-199 | |
| 0004 | 24 | | GK | | 11-0 | 23-51-21 | D00451 | | 5 | | | TB0065X | A010 | BJ | | ALL | |
| 0005 | 24 | | GK | | 11-0 | 23-51-21 | D00451 | | 6 | | | TB0065Y | C008 | BJ | | ALL | |
| 0006 | 24 | | GK | | 11-0 | 23-51-21 | D00451 | | 7 | | | TB0065X | C010 | BJ | | ALL | |
| 0007 | 20 | | GA | | 6-0 | 23-51-21 | D00451 | | 4 | | | GD00742 | DC.. | 2 | | 001-099 | |
| 0007 | 20 | | GA | | 4-0 | 23-51-21 | D00451 | | 4 | | | GD00742 | DC.. | 2 | | 115-199 | |
| 0008 | 24 | | GK | | 9-0 | 23-51-21 | D00451 | | 22 | | | SP00107 | | 9 | | 001-099 | |
| 0008 | 24 | | GK | | 7-0 | 23-51-21 | D00451 | | 22 | | | SP00107 | | 9 | | 115-199 | |
| 0009 | 24 | | GK | | 19-0 | 23-51-21 | D00451 | | 19 | | | D00537 | | 6 | | ALL | |
| 0010 | 24 | | GK | | 19-0 | 23-51-21 | D00451 | | 20 | | | D00537 | | 4 | | ALL | |
| 0011 | 24 | | GK | | 19-0 | 23-51-21 | D00451 | | 21 | | | D00537 | | 7 | | ALL | |
| 0012 | 24 | | GK | | 1-0 | 23-51-21 | D00451 | | 23 | | | D00451 | | 24 | | ALL | |
| 0013 | 20 | | GA | | 6-0 | 23-51-21 | D00451 | | | | AA | GD01650 | ST.. | 2 | | 001-099 | |
| 0013 | 20 | | GA | | 5-0 | 23-51-21 | D00451 | | | | AA | GD01650 | ST.. | 2 | | 115-199 | |
| 0016 | 20 | | GA | | 5-0 | 33-13-52 | D00763 | | 1 | | | TB0058Z | | 3 | BJ | 115-199 | |
| 0017 | 20 | | GA | | 5-0 | 33-13-52 | D00763 | | 2 | | | GD01827 | AC.. | 2 | | 115-199 | |
| 0018 | 24 | | GK | | 34-0 | 23-51-51 | D00455 | | 5 | | | D00763 | | 5 | | 115-199 | |
| 0019 | 24 | | GK | | 34-0 | 23-51-51 | D00455 | | 6 | | | D00763 | | 4 | | 115-199 | |
| 0020 | 24 | | GK | | 34-0 | 23-51-51 | D00455 | | 7 | | | D00763 | | 3 | | 115-199 | |
| 0021 | 22 | | GA | | 19-0 | 23-51-51 | D00455 | | 31 | | | TB0113Y | C017 | BJ | | 115-199 | |
| 2001B | 24 | | GL | AA | 19-0 | 23-51-21 | D00451 | | 17 | | | D00537 | | 2 | | ALL | |
| 2001R | 24 | | GL | AA | 0-0 | 23-51-21 | D00451 | | 18 | | | D00537 | | 1 | | ALL | |
| 2002B | 24 | | GL | AB | 17-0 | 23-51-21 | D00451 | | 13 | | | D40121 | | 1 | VY | 001-099 | |
| 2002B | 24 | | GL | AB | 17-0 | 23-51-21 | D00451 | | 13 | | | D00529 | | 2 | | 115-199 | |
| 2002R | 24 | | GL | AB | 0-0 | 23-51-21 | D00451 | | 14 | | | D40123 | | 1 | VR | 001-099 | |
| 2002R | 24 | | GL | AB | 0-0 | 23-51-21 | D00451 | | 14 | | | D00529 | | 1 | | 115-199 | |
| 2003B | 24 | | PL | AK | 6-0 | 23-51-21 | TB0058X | | A007 | BJ | | D00451 | | 28 | | 115-199 | |
| 2003R | 24 | | PL | AK | 0-0 | 23-51-21 | TB0058X | | A008 | BJ | | D00451 | | 27 | | 115-199 | |
| 2501B | 24 | | G2 | AC | 17-0 | 23-51-21 | D00451 | | 15 | | | D40127 | | 1 | VG | 001-099 | |
| 2501B | 24 | | G2 | AC | 17-0 | 23-51-21 | D00451 | | 15 | | | D00529 | | 4 | | 115-199 | |
| 2501R | 24 | | G2 | AC | 0-0 | 23-51-21 | D00451 | | 16 | | | D40125 | | 1 | VS | 001-099 | |
| 2501R | 24 | | G2 | AC | 0-0 | 23-51-21 | D00451 | | 16 | | | D00529 | | 3 | | 115-199 | |
| 2501Z | | | | AC | 0-0 | 23-51-21 | D00451 | | | | AA | D40125 | DED | | | 001-099 | |
| 2501Z | | | | AC | 0-0 | 23-51-21 | D00451 | | | | AA | D00529 | DED | | | 115-199 | |
| 2502B | 24 | | G2 | AD | 20-0 | 23-51-21 | D00451 | | 8 | | | D00535 | | 2 | | ALL | |
| 2502R | 24 | | G2 | AD | 0-0 | 23-51-21 | D00451 | | 9 | | | D00535 | | 1 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2290

Page 2

Dec 18/2007



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2295 | 286N2295 | | | F/O INTERPHONE-P8 TO F/O AUX PNL(P14) (continued) | | | | | | | | | | | |
| 2502Z | | | | AD | 0-0 | 23-51-21 | D00451 | | | AA | D00535 | 3 | | | ALL |
| 2504B | 24 | G2 | | AG | 11-0 | 23-51-21 | D00451 | 29 | | | TB0065Y | A011 | BJ | | 009 |
| 2504R | 24 | G2 | | AG | 0-0 | 23-51-21 | D00451 | 30 | | | TB0065Y | C011 | BJ | | 009 |
| 2504Z | | | | AG | 0-0 | 23-51-21 | D00451 | DED | | | TB0065Y | A012 | BJ | | 009 |
| 3501B | 24 | G3 | | AE | 16-0 | 23-51-21 | D00451 | 12 | | | SM00004 | | 9 | | ALL |
| 3501R | 24 | G3 | | AE | 0-0 | 23-51-21 | D00451 | 10 | | | SM00005 | | 9 | | ALL |
| 3501Y | 24 | G3 | | AE | 0-0 | 23-51-21 | D00451 | 11 | | | SM00006 | | 9 | | ALL |
| 3501Z | | | | AE | 0-0 | 23-51-21 | D00451 | | | AA | SM00004 | DED | | | ALL |
| 5001B | 24 | G2 | | AF | 11-0 | 23-51-21 | D00451 | 29 | | | TB0065Y | A011 | BJ | | 115-199 |
| 5001R | 24 | G2 | | AF | 0-0 | 23-51-21 | D00451 | 30 | | | TB0065Y | C011 | BJ | | 115-199 |
| 5001Z | | | | AF | 0-0 | 23-51-21 | D00451 | | | AA | TB0065Y | A012 | BJ | | 115-199 |
| A-AE | | | | | 0-0 | 23-51-21 | D00531 | BLU | | | SM00004 | | 9 | | ALL |
| A-AF | | | | | 0-0 | 23-51-21 | D00531 | BLK | | | SM00006 | | 9 | | ALL |
| A-AG | | | | | 0-0 | 23-51-21 | D00533 | RED | | | SM00005 | | 9 | | ALL |
| A-AH | | | | | 0-0 | 23-51-21 | D00533 | BLU | | | SM00004 | | 9 | | ALL |
| A-AI | | | | | 0-0 | 23-51-21 | D00533 | BLK | | | SM00006 | | 9 | | ALL |
| W2297 | 286N2297 | | | CAPT INTERPHONE-P8 TO CAPT AUX PNL | | | | | | | | | | | |
| 0001 | 16 | GA | | | 5-0 | 33-13-52 | D00339 | 1 | 16 | | TB0159F | A010 | 2 | | ALL |
| 0002 | 16 | GA | | | 5-0 | 33-13-52 | D00339 | 2 | 16 | | GD01649 | AC.. | 2 | | ALL |
| 0003 | 22 | GA | | | 5-0 | 23-51-11 | D00339 | 3 | | | TB0059X | A007 | BJ | | ALL |
| 0004 | 24 | GK | | | 9-0 | 23-51-11 | D00339 | 5 | | | TB0065X | A009 | BJ | | ALL |
| 0005 | 24 | GK | | | 9-0 | 23-51-11 | D00339 | 6 | | | TB0065Y | A008 | BJ | | ALL |
| 0006 | 24 | GK | | | 9-0 | 23-51-11 | D00339 | 7 | | | TB0065X | C009 | BJ | | ALL |
| 0007 | 20 | GA | | | 5-0 | 23-51-11 | D00339 | 4 | | | GD01649 | DC.. | 2 | | ALL |
| 0008 | 24 | GK | | | 9-0 | 23-51-11 | D00339 | 22 | | | SP00107 | | 9 | | 115-199 |
| 0009 | 24 | GK | | | 23-0 | 23-51-11 | D00339 | 19 | | | D00547 | 6 | | | 001-099 |
| 0009 | 24 | GK | | | 22-0 | 23-51-11 | D00339 | 19 | | | D00547 | 6 | | | 115-199 |
| 0010 | 24 | GK | | | 23-0 | 23-51-11 | D00339 | 20 | | | D00547 | 4 | | | 001-099 |
| 0010 | 24 | GK | | | 22-0 | 23-51-11 | D00339 | 20 | | | D00547 | 4 | | | 115-199 |
| 0011 | 24 | GK | | | 23-0 | 23-51-11 | D00339 | 21 | | | D00547 | 7 | | | 001-099 |
| 0011 | 24 | GK | | | 22-0 | 23-51-11 | D00339 | 21 | | | D00547 | 7 | | | 115-199 |
| 0012 | 24 | GK | | | 1-0 | 23-51-11 | D00339 | 23 | | | D00339 | 24 | | | ALL |
| 0013 | 20 | GA | | | 5-0 | 23-51-11 | D00339 | | | AA | GD01649 | ST.. | 2 | | ALL |
| 0022 | 24 | GK | | | 9-0 | 23-51-11 | D00339 | 22 | | | SP00107 | | 9 | | 001-099 |
| 2001B | 24 | GL | AA | | 23-0 | 23-51-11 | D00339 | 17 | | | D00547 | 2 | | | 001-099 |
| 2001B | 24 | GL | AA | | 22-0 | 23-51-11 | D00339 | 17 | | | D00547 | 2 | | | 115-199 |
| 2001R | 24 | GL | AA | | 0-0 | 23-51-11 | D00339 | 18 | | | D00547 | 1 | | | ALL |
| 2002B | 24 | GL | AB | | 21-0 | 23-51-11 | D00339 | 13 | | | D40101 | 1 | VY | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2290

Page 3

Dec 18/2007



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2297 | 286N2297 | | | CAPT INTERPHONE-P8 TO CAPT AUX PNL (continued) | | | | | | | | | | | |
| 2002B | 24 | GL | AB | | 20-0 | 23-51-11 | D00339 | | | | D00539 | 2 | | | 115-199 |
| 2002R | 24 | GL | AB | | 0-0 | 23-51-11 | D00339 | | | | D40107 | 1 | VR | | 001-099 |
| 2002R | 24 | GL | AB | | 0-0 | 23-51-11 | D00339 | | | | D00539 | 1 | | | 115-199 |
| 2003B | 24 | PL | AK | | 4-10 | 23-51-11 | D00339 | | | | TB0059X | A014 | BJ | | 115-199 |
| 2003R | 24 | PL | AK | | 0-0 | 23-51-11 | D00339 | | | | TB0059X | A015 | BJ | | 115-199 |
| 2501B | 24 | G2 | AC | | 21-0 | 23-51-11 | D00339 | | | | D40115 | 1 | VG | | 001-099 |
| 2501B | 24 | G2 | AC | | 20-0 | 23-51-11 | D00339 | | | | D00539 | 4 | | | 115-199 |
| 2501R | 24 | G2 | AC | | 0-0 | 23-51-11 | D00339 | | | | D40111 | 1 | VS | | 001-099 |
| 2501R | 24 | G2 | AC | | 0-0 | 23-51-11 | D00339 | | | | D00539 | 3 | | | 115-199 |
| 2501Z | | | AC | | 0-0 | 23-51-11 | D00339 | | | AA | D40111 | DED | | | 001-099 |
| 2501Z | | | AC | | 0-0 | 23-51-11 | D00339 | | | AA | D00539 | DED | | | 115-199 |
| 2502B | 24 | G2 | AE | | 24-0 | 23-51-11 | D00339 | | | | D00545 | 2 | | | 001-099 |
| 2502B | 24 | G2 | AE | | 23-0 | 23-51-11 | D00339 | | | | D00545 | 2 | | | 115-199 |
| 2502R | 24 | G2 | AE | | 0-0 | 23-51-11 | D00339 | | | | D00545 | 1 | | | ALL |
| 2502Z | | | AE | | 0-0 | 23-51-11 | D00339 | | | AA | D00545 | 3 | | | ALL |
| 2504B | 24 | G2 | AG | | 9-0 | 23-51-11 | D00339 | | | | TB0065Y | A011 | BJ | | 009 |
| 2504R | 24 | G2 | AG | | 0-0 | 23-51-11 | D00339 | | | | TB0065Y | C011 | BJ | | 009 |
| 2504Z | | | AG | | 0-0 | 23-51-11 | D00339 | | | DED | TB0065Y | A012 | BJ | | 009 |
| 3501B | 24 | G3 | AD | | 20-0 | 23-51-11 | D00339 | | | | SM00004 | | 9 | | 001-099 |
| 3501B | 24 | G3 | AD | | 19-0 | 23-51-11 | D00339 | | | | SM00004 | | 9 | | 115-199 |
| 3501R | 24 | G3 | AD | | 0-0 | 23-51-11 | D00339 | | | | SM00005 | | 9 | | ALL |
| 3501Y | 24 | G3 | AD | | 0-0 | 23-51-11 | D00339 | | | | SM00006 | | 9 | | ALL |
| 3501Z | | | AD | | 0-0 | 23-51-11 | D00339 | | | AA | SM00REF | DED | | | 001-099 |
| 3501Z | | | AD | | 0-0 | 23-51-11 | D00339 | | | AA | SM00004 | DED | | | 115-199 |
| 5001B | 24 | G2 | AF | | 9-0 | 23-51-11 | D00339 | | | | TB0065Y | A011 | BJ | | 115-199 |
| 5001R | 24 | G2 | AF | | 0-0 | 23-51-11 | D00339 | | | | TB0065Y | C011 | BJ | | 115-199 |
| 5001Z | | | AF | | 0-0 | 23-51-11 | D00339 | | | DED | TB0065Y | A012 | BJ | | 115-199 |
| A-AD | | | | | 0-0 | 23-51-11 | D00543 | | | | SM00005 | | 9 | | ALL |
| A-AE | | | | | 0-0 | 23-51-11 | D00543 | | | | SM00004 | | 9 | | ALL |
| A-AF | | | | | 0-0 | 23-51-11 | D00543 | | | | SM00006 | | 9 | | ALL |
| A-AH | | | | | 0-0 | 23-51-11 | D00541 | | | | SM00004 | | 9 | | ALL |
| A-AI | | | | | 0-0 | 23-51-11 | D00541 | | | | SM00006 | | 9 | | ALL |
| W2299 | 286N2299 | | | FLIGHT DATA RECORDER CONTROL,P61 TO E3-3 | | | | | | | | | | | |
| 0001 | 22 | GA | | | 40-0 | 31-31-01 | D40003P | | | | D41519P | 1 | | | 001-099 |
| 0001 | 22 | GA | | | 40-0 | 31-31-11 | D40003P | | | | D41519P | 1 | | | 115-199 |
| 0002 | 22 | GA | | | 40-0 | 31-31-01 | D40003P | | | | D41519P | 2 | | | 001-099 |
| 0002 | 22 | GA | | | 40-0 | 31-31-11 | D40003P | | | | D41519P | 2 | | | 115-199 |
| 0003 | 22 | GA | | | 40-0 | SPARE | D40003P | | | | D41519P | 3 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2290

Page 4

Dec 18/2007



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2299 | 286N2299 | | | FLIGHT DATA RECORDER CONTROL,P61 TO E3-3 (continued) | | | | | | | | | | | |
| 0004 | 22 | | GA | | 40-0 | SPARE | D40003P | | 4 | | D41519P | | 4 | | 001-099 |
| 0004 | 22 | | GA | | 40-0 | 31-31-11 | D40003P | | 4 | | D41519P | | 4 | | 115-199 |
| 0005 | 24 | | GK | | 40-0 | 31-31-01 | D40003P | | 5 | | D41519P | | 5 | | 001-099 |
| 0005 | 24 | | GK | | 40-0 | 31-31-11 | D40003P | | 5 | | D41519P | | 5 | | 115-199 |
| 0006 | 24 | | GK | | 40-0 | 31-31-01 | D40003P | | 6 | | D41519P | | 6 | | 001-099 |
| 0006 | 24 | | GK | | 40-0 | 31-31-11 | D40003P | | 6 | | D41519P | | 6 | | 115-199 |
| 0007 | 24 | | GK | | 40-0 | 31-31-01 | D40003P | | 21 | | D41519P | | 28 | | 001-099 |
| 0007 | 24 | | GK | | 40-0 | 31-31-11 | D40003P | | 21 | | D41519P | | 28 | | 115-199 |
| 0008 | 22 | | GA | | 40-0 | SPARE | D40003P | | 18 | | D41519P | | 18 | | 115-199 |
| 0009 | 22 | | GA | | 40-0 | SPARE | D40003P | | 19 | | D41519P | | 19 | | 115-199 |
| 0010 | 22 | | GA | | 40-0 | SPARE | D40003P | | 20 | | D41519P | | 20 | | 001-099 |
| 0010 | 22 | | GA | | 40-0 | 31-31-11 | D40003P | | 20 | | D41519P | | 20 | | 115-199 |
| 0011 | 22 | | GA | | 40-0 | 31-31-01 | D40003P | | 22 | | D41519P | | 22 | | 001-099 |
| 0011 | 22 | | GA | | 40-0 | 31-31-11 | D40003P | | 22 | | D41519P | | 22 | | 115-199 |
| 0012 | 24 | | GK | | 40-0 | 31-31-01 | D40003P | | 23 | | D41519P | | 26 | | 001-099 |
| 0012 | 24 | | GK | | 40-0 | 31-31-11 | D40003P | | 23 | | D41519P | | 26 | | 115-199 |
| 0013 | 24 | | GK | | 40-0 | 31-31-01 | D40003P | | 24 | | D41519P | | 24 | | 001-099 |
| 0013 | 24 | | GK | | 40-0 | 31-31-11 | D40003P | | 24 | | D41519P | | 24 | | 115-199 |
| 0014 | 24 | | GK | | 40-0 | 31-31-01 | D40003P | | 31 | | D41519P | | 31 | | 001-099 |
| 0014 | 24 | | GK | | 40-0 | 31-31-11 | D40003P | | 31 | | D41519P | | 31 | | 115-199 |
| 0015 | 22 | | GA | | 40-0 | SPARE | D40003P | | 25 | | D41519P | | 25 | | 001-099 |
| 0015 | 22 | | GA | | 40-0 | SPARE | D40003P | | 25 | | D41519P | | 30 | | 115-199 |
| 5001B | 24 | | G2 | AA | 40-0 | SPARE | D40003P | | 11 | | D41519P | | 11 | | 001-099 |
| 5001B | 24 | | G2 | AA | 40-0 | 31-31-11 | D40003P | | 11 | | D41519P | | 11 | | 115-199 |
| 5001R | 24 | | G2 | AA | 0-0 | SPARE | D40003P | | 10 | | D41519P | | 10 | | 001-099 |
| 5001R | 24 | | G2 | AA | 0-0 | 31-31-11 | D40003P | | 10 | | D41519P | | 10 | | 115-199 |
| 5001Z | | | | AA | 0-0 | 31-31-11 | D40003P | | 7 | | D41519P | | 23 | | ALL |
| 5002B | 24 | | G2 | AB | 40-0 | 31-31-01 | D40003P | | 15 | | D41519P | | 15 | | 001-099 |
| 5002B | 24 | | G2 | AB | 40-0 | 31-31-11 | D40003P | | 15 | | D41519P | | 15 | | 115-199 |
| 5002R | 24 | | G2 | AB | 0-0 | 31-31-01 | D40003P | | 14 | | D41519P | | 14 | | 001-099 |
| 5002R | 24 | | G2 | AB | 0-0 | 31-31-11 | D40003P | | 14 | | D41519P | | 14 | | 115-199 |
| 5002Z | | | | AB | 0-0 | 31-31-01 | D40003P | | 32 | | D41519P | | 27 | | 001-099 |
| 5002Z | | | | AB | 0-0 | 31-31-11 | D40003P | | 32 | | D41519P | | 27 | | 115-199 |
| 5003B | 24 | | G2 | AC | 40-0 | SPARE | D40003P | | 17 | | D41519P | | 17 | | 001-099 |
| 5003B | 24 | | G2 | AC | 40-0 | 31-31-11 | D40003P | | 17 | | D41519P | | 17 | | 115-199 |
| 5003R | 24 | | G2 | AC | 0-0 | SPARE | D40003P | | 16 | | D41519P | | 16 | | 001-099 |
| 5003R | 24 | | G2 | AC | 0-0 | 31-31-11 | D40003P | | 16 | | D41519P | | 16 | | 115-199 |
| 5003Z | | | | AC | 0-0 | SPARE | D40003P | | 33 | | D41519P | | 29 | | 001-099 |
| 5003Z | | | | AC | 0-0 | 31-31-11 | D40003P | | 33 | | D41519P | | 29 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2290

Page 5

Dec 18/2007



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2299 | 286N2299 | | | FLIGHT DATA RECORDER CONTROL,P61 TO E3-3 (continued) | | | | | | | | | | | |
| 5004B | 24 | G2 | AD | | 40-0 | 31-31-01 | D40003P | | 9 | | D41519P | | 9 | | 001-099 |
| 5004B | 24 | G2 | AD | | 40-0 | 31-31-11 | D40003P | | 9 | | D41519P | | 9 | | 115-199 |
| 5004R | 24 | G2 | AD | | 0-0 | 31-31-01 | D40003P | | 8 | | D41519P | | 8 | | 001-099 |
| 5004R | 24 | G2 | AD | | 0-0 | 31-31-11 | D40003P | | 8 | | D41519P | | 8 | | 115-199 |
| 5004Z | | | | AD | 0-0 | 31-31-01 | D40003P | | 41 | | D41519P | | 21 | | 001-099 |
| 5004Z | | | | AD | 0-0 | 31-31-11 | D40003P | | 41 | | D41519P | | 21 | | 115-199 |
| 5005B | 24 | G2 | AE | | 40-0 | SPARE | D40003P | | 19 | | D41519P | | 19 | | 001-099 |
| 5005R | 24 | G2 | AE | | 0-0 | SPARE | D40003P | | 18 | | D41519P | | 18 | | 001-099 |
| 5005Z | | | | AE | 0-0 | SPARE | D40003P | | 37 | | D41519P | | 30 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2290

Page 6 End

Dec 18/2007



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2301 | 286N2301 | G/S ANTENNA - LEFT | | | | | | | | | | | | | |
| 001CO | | AA | 0-0 | 34-31-11 | D00193 | = C1 | | | D40715P | = C1 | | | ALL | | |
| 001CX | 94 | AA | 1-2 | 34-31-11 | D00193 | = A1 | | | D40715P | = A1 | | | ALL | | |
| W2303 | 286N2303 | G/S ANTENNA - RIGHT | | | | | | | | | | | | | |
| 001CO | | AA | 0-0 | 34-31-21 | D00197 | = C1 | | | D40717P | = C1 | | | ALL | | |
| 001CX | 94 | AA | 1-1 | 34-31-21 | D00197 | = A1 | | | D40717P | = A1 | | | ALL | | |
| W2304 | 286N2304 | WINDOW HEAT-L WINDOW 1 | | | | | | | | | | | | | |
| A-AA | | | 0-0 | 30-41-11 | D03322 | = 1 | | | TB5028 | 1 | E | | ALL | | |
| A-AB | | | 0-0 | 30-41-11 | D03324 | = 1 | | | TB5028 | 1 | E | | ALL | | |
| A-AC | | | 0-0 | 30-41-11 | D03326 | = 1 | | | TB5028 | 2 | E | | ALL | | |
| A-BA | | | 0-0 | 30-41-11 | D03328 | A | | | TB5028 | 3 | E | | ALL | | |
| A-BB | | | 0-0 | 30-41-11 | D03328 | B | | | TB5028 | 4 | E | | ALL | | |
| A-CA | | | 0-0 | 30-41-11 | D03330 | A | | | TB5028 | 5 | E | | ALL | | |
| A-CB | | | 0-0 | 30-41-11 | D03330 | B | | | TB5028 | 6 | E | | ALL | | |
| W2305 | 286N2305 | G/S ANTENNA - CENTER | | | | | | | | | | | | | |
| 001CO | | AA | 0-0 | 34-31-31 | D00201 | = C1 | | | D40719P | = C1 | | | ALL | | |
| 001CX | 94 | AA | 1-2 | 34-31-31 | D00201 | = A1 | | | D40719P | = A1 | | | ALL | | |
| W2306 | 286N2306 | WINDOW HEAT-L WINDOW 2 | | | | | | | | | | | | | |
| A-AA | | | 0-0 | 30-41-12 | D03336 | A | | | D41578J | 5 | | | ALL | | |
| A-AB | | | 0-0 | 30-41-12 | D03336 | B | | | D41578J | 6 | | | ALL | | |
| A-BA | | | 0-0 | 30-41-12 | D03334 | A | | | D41578J | 3 | | | ALL | | |
| A-BB | | | 0-0 | 30-41-12 | D03334 | B | | | D41578J | 4 | | | ALL | | |
| A-CA | | | 0-0 | 30-41-12 | D03332 | C | | | D41578J | 1 | | | ALL | | |
| A-CB | | | 0-0 | 30-41-12 | D03332 | D | | | D41578J | 2 | | | ALL | | |
| W2308 | 286N2308 | WINDOW HEAT-L WINDOW 3 | | | | | | | | | | | | | |
| A-DA | | | 0-0 | 30-41-12 | D03338 | = 1 | | | TB5030 | 1 | C | | ALL | | |
| A-DB | | | 0-0 | 30-41-12 | D04682 | = 1 | | | TB5030 | 2 | C | | ALL | | |
| A-EA | | | 0-0 | 30-41-12 | D03340 | A | | | TB5030 | 3 | C | | ALL | | |
| A-EB | | | 0-0 | 30-41-12 | D03340 | B | | | TB5030 | 4 | C | | ALL | | |
| A-FA | | | 0-0 | 30-41-12 | D03342 | A | | | TB5030 | 5 | C | | ALL | | |
| A-FB | | | 0-0 | 30-41-12 | D03342 | B | | | TB5030 | 6 | C | | ALL | | |
| W2309 | 286N2309 | WEATHER RADAR-LEFT | | | | | | | | | | | | | |
| 0001 | 24 | GK | 19-0 | 34-43-12 | D00159B | C06 | | | D00163 | K | | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W2300

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---------------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2309 | 286N2309 | | | | WEATHER RADAR-LEFT (continued) | | | | | | | | | | | |
| 0001 | 24 | | GK | | 17-3 | 34-43-12 | | D00159B | | C06 | | D00163 | | K | | 115-199 |
| 0002 | 24 | | GK | | 19-0 | 34-43-12 | | D00159B | | D06 | | D00163 | | L | | 001-099 |
| 0002 | 24 | | GK | | 17-3 | 34-43-12 | | D00159B | | D06 | | D00163 | | L | | 115-199 |
| 0003 | 24 | | GK | | 19-0 | 34-43-12 | | D00159B | | D07 | | D00163 | | M | | 001-099 |
| 0003 | 24 | | GK | | 17-3 | 34-43-12 | | D00159B | | D07 | | D00163 | | M | | 115-199 |
| 0004 | 24 | | GK | | 19-0 | 34-43-12 | | D00159B | | B06 | | D00163 | | V | | 001-099 |
| 0004 | 24 | | GK | | 17-3 | 34-43-12 | | D00159B | | B06 | | D00163 | | V | | 115-199 |
| 0005 | 24 | | GK | | 19-0 | 34-43-12 | | D00159B | | E06 | | D00163 | | U | | 001-099 |
| 0005 | 24 | | GK | | 17-3 | 34-43-12 | | D00159B | | E06 | | D00163 | | U | | 115-199 |
| 0006 | 24 | | GK | | 19-0 | 34-43-12 | | D00159B | | E07 | | D00163 | | F- | | 001-099 |
| 0006 | 24 | | GK | | 17-3 | 34-43-12 | | D00159B | | E07 | | D00163 | | F- | | 115-199 |
| 0007 | 24 | | GK | | 19-0 | 34-43-12 | | D00159B | | D08 | | D00163 | | D | | 001-099 |
| 0007 | 24 | | GK | | 17-3 | 34-43-12 | | D00159B | | D08 | | D00163 | | D | | 115-199 |
| 0008 | 20 | | GA | | 5-0 | 34-43-12 | | D00163 | | A | | GD02303 | DC.. | 2 | | 001-099 |
| 0008 | 20 | | GA | | 4-7 | 34-43-12 | | D00163 | | A | | GD02303 | DC.. | 2 | | 115-199 |
| 0009 | 24 | | GK | | 30-0 | 34-43-12 | | D00163 | | G | | SM00001 | | 9 | | 001-099 |
| 0009 | 24 | | GK | | 28-4 | 34-43-12 | | D00163 | | G | | SM00001 | | 9 | | 115-199 |
| 0010 | 24 | | GK | | 6-0 | 34-43-12 | | D41063P | | 10 | | SM00001 | | 9 | | 001-099 |
| 0010 | 24 | | GK | | 5-2 | 34-43-12 | | D41063P | | 10 | | SM00001 | | 9 | | 115-199 |
| 0011 | 24 | | GK | | 5-0 | 34-43-12 | | D41061P | | 6 | | SM00001 | | 9 | | 001-099 |
| 0011 | 24 | | GK | | 4-4 | 34-43-12 | | D41061P | | 6 | | SM00001 | | 9 | | 115-199 |
| 0012 | 22 | | GA | | 6-0 | 34-43-12 | | D00159B | | D11 | | D00477 | | 28 | | 001-099 |
| 0012 | 22 | | GA | | 4-6 | 34-43-12 | | D00159B | | D11 | | D00477 | | 28 | | 115-199 |
| 0013 | 20 | | GA | | 5-0 | 34-43-12 | | D00477 | | 6 | | GD00383 | DC.. | E | | 001-099 |
| 0013 | 20 | | GA | | 4-8 | 34-43-12 | | D00477 | | 6 | | GD00383 | DC.. | E | | 115-199 |
| 0014 | 22 | | GA | | 6-0 | 34-43-12 | | D00159C | | 8 | | D00477 | | 1 | | 001-099 |
| 0014 | 22 | | GA | | 4-6 | 34-43-12 | | D00159C | | 8 | | D00477 | | 1 | | 115-199 |
| 0015 | 22 | | GA | | 6-0 | 34-43-12 | | D00159C | | 3 | | D00477 | | 7 | | 001-099 |
| 0015 | 22 | | GA | | 4-6 | 34-43-12 | | D00159C | | 3 | | D00477 | | 7 | | 115-199 |
| 0016 | 20 | | GA | | 34-0 | 34-43-11 | | D00159C | | 2 | | D41061P | | 1 | | 001-099 |
| 0016 | 20 | | GA | | 32-4 | 34-43-11 | | D00159C | | 2 | | D41061P | | 1 | | 115-199 |
| 0017 | 22 | | GA | | 34-0 | 34-43-11 | | D00159B | | G14 | | D41061P | | 2 | | 001-099 |
| 0017 | 22 | | GA | | 32-4 | 34-43-11 | | D00159B | | G14 | | D41061P | | 2 | | 115-199 |
| 0018 | 22 | | GA | | 5-0 | 34-43-11 | | D00159C | | 7 | | GD02749 | AC.. | 2 | | 001-099 |
| 0018 | 22 | | GA | | 3-6 | 34-43-11 | | D00159C | | 7 | | GD02749 | AC.. | 2 | | 115-199 |
| 0019 | 22 | | GA | | 5-0 | 34-43-11 | | D00159C | | 11 | | GD02749 | DC.. | 2 | | 001-099 |
| 0019 | 22 | | GA | | 3-6 | 34-43-11 | | D00159C | | 11 | | GD02749 | DC.. | 2 | | 115-199 |
| 0023 | 20 | | GA | | 5-0 | 33-13-52 | | D00163 | | P | | TB0059Z | | 1 | BJ | 001-099 |
| 0023 | 20 | | GA | | 5-3 | 33-13-52 | | D00163 | | P | | TB0059Z | | 1 | BJ | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2300

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|--------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W2309 | 286N2309 | | | WEATHER RADAR-LEFT (continued) | | | | | | | | | | | | |
| 0024 | 20 | | GA | | 5-0 | 33-13-52 | D00163 | | E- | | | GD02303 | AC.. | 2 | | 001-099 |
| 0024 | 20 | | GA | | 4-7 | 33-13-52 | D00163 | | E- | | | GD02303 | AC.. | 2 | | 115-199 |
| 0035 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | G01 | VM | | | SM00009 | | W | | 002 |
| 0035 | 24 | | GK | | 1-0 | 34-43-12 | D00159B | F03 | | | | D00159B | F07 | | | 003-008, 010-099 |
| 0038 | 20 | | GA | | 1-6 | 34-43-12 | D00163 | | | | AF | GD02303 | ST.. | 2 | | ALL |
| 0041 | 22 | | GA | | 2-0 | 34-43-12 | D00477 | | 3 | | | GD03149 | ST.. | E | *1 | 001-099 |
| 0041 | 22 | | GA | | 1-3 | 34-43-12 | D00477 | | 3 | | | GD03149 | ST.. | E | *1 | 115-199 |
| 0042 | 22 | | GA | | 2-0 | 34-43-12 | D00477 | | 18 | | | GD03149 | ST.. | E | *1 | 001-099 |
| 0042 | 22 | | GA | | 1-3 | 34-43-12 | D00477 | | 18 | | | GD03149 | ST.. | E | *1 | 115-199 |
| 0043 | 22 | | GA | | 2-0 | 34-43-12 | D00477 | | 15 | | | GD03149 | ST.. | E | *1 | 001-099 |
| 0043 | 22 | | GA | | 1-3 | 34-43-12 | D00477 | | 15 | | | GD03149 | ST.. | E | *1 | 115-199 |
| 0044 | 22 | | GA | | 2-0 | 34-43-12 | D00477 | | 11 | | | GD03149 | ST.. | E | *1 | 001-099 |
| 0044 | 22 | | GA | | 1-3 | 34-43-12 | D00477 | | 11 | | | GD03149 | ST.. | E | *1 | 115-199 |
| 0045 | 22 | | GA | | 2-0 | 34-43-12 | D00477 | | 21 | | | GD03149 | ST.. | E | *2 | 001-099 |
| 0045 | 22 | | GA | | 1-3 | 34-43-12 | D00477 | | 21 | | | GD03149 | ST.. | E | *2 | 115-199 |
| 0046 | 22 | | GA | | 2-0 | 34-43-12 | D00477 | | 35 | | | GD03149 | ST.. | E | *2 | 001-099 |
| 0046 | 22 | | GA | | 1-3 | 34-43-12 | D00477 | | 35 | | | GD03149 | ST.. | E | *2 | 115-199 |
| 0047 | 22 | | GA | | 2-0 | 34-43-12 | D00477 | | 32 | | | GD03149 | ST.. | E | *2 | 001-099 |
| 0047 | 22 | | GA | | 1-3 | 34-43-12 | D00477 | | 32 | | | GD03149 | ST.. | E | *2 | 115-199 |
| 0048 | 22 | | GA | | 2-0 | 34-43-12 | D00477 | | 29 | | | GD03149 | ST.. | E | *2 | 001-099 |
| 0048 | 22 | | GA | | 1-3 | 34-43-12 | D00477 | | 29 | | | GD03149 | ST.. | E | *2 | 115-199 |
| 0068 | 22 | | GA | | 65-0 | 34-43-14 | D41823P | | 12 | | | D00159B | F14 | | | 002 |
| 0070 | 22 | | GA | | 65-0 | 34-43-14 | D41238P | | 55 | | | D00159B | D01 | | | 002 |
| 0072 | 22 | | GA | | 65-0 | 34-43-14 | D41823P | | 11 | | | D00159B | F15 | | | 002 |
| 0073 | 22 | | GA | | 65-0 | 34-43-14 | D00159B | | B14 | | | D41445P | | 31 | | 002 |
| 0074 | 22 | | GA | | 65-0 | 34-43-14 | D00159B | | B09 | | | D41879P | | 50 | | 002 |
| 0075 | 22 | | GA | | 65-0 | 34-43-14 | D00159B | | B10 | | | D41867P | | 2 | | 002 |
| 0076 | 22 | | GA | | 65-0 | 34-43-14 | D00159B | | E02 | VM | | D41867P | | 16 | | 002 |
| 0077 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | A02 | | | SM00010 | | | W | 002 |
| 0078 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | A03 | VM | | SM00010 | | | W | 002 |
| 0079 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | F07 | | | SM00009 | | | W | 002 |
| 0080 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | C03 | VM | | SM00009 | | | W | 002 |
| 0084 | 22 | | GA | | 65-0 | 34-43-14 | D00159B | | K10 | | | D41487P | | 48 | | 002 |
| 0087 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | D10 | | | SM00010 | | | W | 002 |
| 0088 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | E01 | | | SM00010 | | | W | 002 |
| 0089 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | E09 | | | SM00009 | | | W | 002 |
| 0091 | 22 | | GA | | 65-0 | 34-43-15 | D41238P | | 22 | | | D00159B | F01 | | | 002 |
| 0093 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | F02 | | | SM00009 | | | W | 002 |
| 0096 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | | F03 | | | SM00009 | | | W | 002 |

WIRE LIST

D280N032

91-21-11

Section W2300

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|--------------------------------|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| WEATHER RADAR-LEFT (continued) | | | | | | | | | | | | | | | |
| 0501 | 22 | | GA | | 8-0 | 34-43-14 | D00159B | A04 | | | SM00010 | | W | | 002 |
| 0502 | 22 | | GA | | 8-0 | 34-43-14 | SM00010 | | W | | SM00009 | | W | | 002 |
| 2501B | 22 | | GU | AA | 6-0 | 34-43-12 | D00477 | 4 | | | D00159B | C14 | | | 001-099 |
| 2501B | 22 | | GU | AA | 4-6 | 34-43-12 | D00477 | 4 | | | D00159B | C14 | | | 115-199 |
| 2501R | 22 | | GU | AA | 0-0 | 34-43-12 | D00477 | 5 | | | D00159B | C13 | | | ALL |
| 2501Z | | | | AA | 0-0 | 34-43-12 | GD03153 | ST.. | E | *1 | D00159B | | | AB | ALL |
| 2502B | 22 | | GU | AB | 6-0 | 34-43-12 | D00477 | 16 | | | D00159B | E14 | | | 001-099 |
| 2502B | 22 | | GU | AB | 4-6 | 34-43-12 | D00477 | 16 | | | D00159B | E14 | | | 115-199 |
| 2502R | 22 | | GU | AB | 0-0 | 34-43-12 | D00477 | 17 | | | D00159B | E13 | | | ALL |
| 2502Z | | | | AB | 0-0 | 34-43-12 | GD03153 | ST.. | E | *1 | D00159B | | | AB | ALL |
| 2503B | 22 | | GU | AC | 6-0 | 34-43-12 | D00477 | 9 | | | D00159B | A14 | | | 001-099 |
| 2503B | 22 | | GU | AC | 4-6 | 34-43-12 | D00477 | 9 | | | D00159B | A14 | | | 115-199 |
| 2503R | 22 | | GU | AC | 0-0 | 34-43-12 | D00477 | 10 | | | D00159B | A13 | | | ALL |
| 2503Z | | | | AC | 0-0 | 34-43-12 | GD03153 | ST.. | E | *1 | D00159B | | | AA | ALL |
| 2504B | 22 | | GU | AD | 6-0 | 34-43-12 | D00477 | 33 | | | D00159B | D15 | | | 001-099 |
| 2504B | 22 | | GU | AD | 4-6 | 34-43-12 | D00477 | 33 | | | D00159B | D15 | | | 115-199 |
| 2504R | 22 | | GU | AD | 0-0 | 34-43-12 | D00477 | 34 | | | D00159B | E15 | | | ALL |
| 2504Z | | | | AD | 0-0 | 34-43-12 | GD03153 | ST.. | E | *1 | D00159B | | | AA | ALL |
| 2505B | 22 | | GU | AE | 6-0 | 34-43-12 | D00477 | 30 | | | D00159B | B15 | | | 001-099 |
| 2505B | 22 | | GU | AE | 4-6 | 34-43-12 | D00477 | 30 | | | D00159B | B15 | | | 115-199 |
| 2505R | 22 | | GU | AE | 0-0 | 34-43-12 | D00477 | 31 | | | D00159B | A15 | | | ALL |
| 2505Z | | | | AE | 0-0 | 34-43-12 | GD03153 | ST.. | E | *2 | D00159B | | | AA | ALL |
| 2506B | 24 | | G2 | AF | 19-0 | 34-43-12 | D00159B | B08 | | | D00163 | J- | | | 001-099 |
| 2506B | 24 | | G2 | AF | 17-3 | 34-43-12 | D00163 | J- | | | D00159B | B08 | | | 115-199 |
| 2506R | 24 | | G2 | AF | 0-0 | 34-43-12 | D00159B | B07 | | | D00163 | H- | | | 001-099 |
| 2506R | 24 | | G2 | AF | 0-0 | 34-43-12 | D00163 | H- | | | D00159B | B07 | | | 115-199 |
| 2506Z | | | | AF | 0-0 | 34-43-12 | GD02749 | ST.. | 2 | | D00163 | | | AF | 001-099 |
| 2506Z | | | | AF | 0-0 | 34-43-12 | D00163 | | | AF | GD02749 | ST.. | 2 | | 115-199 |
| 3501B | 22 | | GV | AH | 6-0 | 34-43-12 | D00477 | 8 | | | D00159B | C11 | | | 001-099 |
| 3501B | 22 | | GV | AH | 4-6 | 34-43-12 | D00477 | 8 | | | D00159B | C11 | | | 115-199 |
| 3501R | 22 | | GV | AH | 0-0 | 34-43-12 | D00477 | 2 | | | D00159B | C10 | | | ALL |
| 3501Y | 22 | | GV | AH | 0-0 | 34-43-12 | D00477 | 19 | | | D00159B | C12 | | | ALL |
| 3501Z | | | | AH | 0-0 | 34-43-12 | GD03153 | ST.. | E | *2 | D00159B | | | AB | ALL |
| 3502B | 22 | | GV | AI | 6-0 | 34-43-12 | D00477 | 13 | | | D00159B | E11 | | | 001-099 |
| 3502B | 22 | | GV | AI | 4-6 | 34-43-12 | D00477 | 13 | | | D00159B | E11 | | | 115-199 |
| 3502R | 22 | | GV | AI | 0-0 | 34-43-12 | D00477 | 14 | | | D00159B | E10 | | | ALL |
| 3502Y | 22 | | GV | AI | 0-0 | 34-43-12 | D00477 | 12 | | | D00159B | E12 | | | ALL |
| 3502Z | | | | AI | 0-0 | 34-43-12 | GD03153 | ST.. | E | *2 | D00159B | | | AB | ALL |
| 3503B | 22 | | GV | AJ | 6-0 | 34-43-12 | D00477 | 37 | | | D00159B | A11 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2300

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2309 | 286N2309 | | | WEATHER RADAR-LEFT (continued) | | | | | | | | | | | |
| 3503B | 22 | | GV | AJ | 4-6 | 34-43-12 | D00477 | 37 | | | D00159B | A11 | | | 115-199 |
| 3503R | 22 | | GV | AJ | 0-0 | 34-43-12 | D00477 | 20 | | | D00159B | A10 | | | ALL |
| 3503Y | 22 | | GV | AJ | 0-0 | 34-43-12 | D00477 | 36 | | | D00159B | A12 | | | ALL |
| 3503Z | | | | AJ | 0-0 | 34-43-12 | GD03153 | ST.. | E | *2 | D00159B | | | AA | ALL |
| 5001B | 24 | | G2 | AL | 34-0 | 34-43-11 | D41061P | 9 | | | D00159B | B04 | | | 001-099 |
| 5001B | 24 | | G2 | AL | 32-4 | 34-43-11 | D41061P | 9 | | | D00159B | B04 | | | 115-199 |
| 5001R | 24 | | G2 | AL | 0-0 | 34-43-11 | D41061P | 8 | | | D00159B | B03 | | | ALL |
| 5001Z | | | | AL | 0-0 | 34-43-11 | D41061P | 7 | | | GD02749 | ST.. | 2 | | ALL |
| 5002B | 24 | | G2 | AM | 35-0 | 34-43-11 | D41063P | 12 | | | D00159B | J04 | | | 001-099 |
| 5002B | 24 | | G2 | AM | 33-2 | 34-43-11 | D41063P | 12 | | | D00159B | J04 | | | 115-199 |
| 5002R | 24 | | G2 | AM | 0-0 | 34-43-11 | D41063P | 11 | | | D00159B | J03 | | | ALL |
| 5002Z | | | | AM | 0-0 | 34-43-11 | D41063P | 13 | | | GD02749 | ST.. | 2 | | ALL |
| 5003B | 24 | | G2 | BA | 30-0 | 34-46-12 | D41063P | 15 | | | TB0065Y | A011 | BJ | | 009 |
| 5003B | 24 | | G2 | AT | 29-6 | 34-46-12 | D41063P | 15 | | | TB0065Y | A011 | BJ | | 115-199 |
| 5003R | 24 | | G2 | BA | 0-0 | 34-46-12 | D41063P | 14 | | | TB0065Y | C011 | BJ | | 009 |
| 5003R | 24 | | G2 | AT | 0-0 | 34-46-12 | D41063P | 14 | | | TB0065Y | C011 | BJ | | 115-199 |
| 5003Z | | | | BA | 0-0 | 34-46-12 | D41063P | 16 | | | TB0065Y | A012 | BJ | | 009 |
| 5003Z | | | | AT | 0-0 | 34-46-12 | D41063P | 16 | | | TB0065Y | A012 | BJ | | 115-199 |
| 5006B | 22 | | GU | AG | 65-0 | 34-43-14 | D41238P | 17 | | | D00159B | C02 | VM | | 002 |
| 5006R | 22 | | GU | AG | 0-0 | 34-43-14 | D41238P | 16 | | | D00159B | C01 | VM | | 002 |
| 5006Z | | | | AG | 0-0 | 34-43-14 | D41238P | 18 | | | D00159B | DED | | | 002 |
| 5007B | 22 | | GU | AK | 65-0 | 34-43-14 | D41238P | 14 | | | D00159B | K12 | | | 002 |
| 5007R | 22 | | GU | AK | 0-0 | 34-43-14 | D41238P | 13 | | | D00159B | K11 | | | 002 |
| 5007Z | | | | AK | 0-0 | 34-43-14 | D41238P | 15 | | | D00159B | | | FA | 002 |
| 5008B | 22 | | GU | AW | 65-0 | 34-43-14 | D41063P | 23 | | | D00159B | J10 | | | 002 |
| 5008R | 22 | | GU | AW | 0-0 | 34-43-14 | D41063P | 22 | | | D00159B | J09 | | | 002 |
| 5008Z | | | | AW | 0-0 | 34-43-14 | D41063P | 24 | | | D00159B | | | FB | 002 |
| 5009B | 22 | | GU | AU | 65-0 | 34-43-14 | D41379P | 25 | | | D00159B | A06 | VM | | 002 |
| 5009R | 22 | | GU | AU | 0-0 | 34-43-14 | D41379P | 24 | | | D00159B | A05 | VM | | 002 |
| 5009Z | | | | AU | 0-0 | 34-43-14 | D41379P | 26 | | | D00159B | DED | | | 002 |
| 5010B | 22 | | GU | AT | 65-0 | 34-43-14 | D00159B | K09 | | | SP00487 | | 9 | | 002 |
| 5010R | 22 | | GU | AT | 0-0 | 34-43-14 | D00159B | K08 | | | SP00485 | | 9 | | 002 |
| 5010Z | | | | AT | 0-0 | 34-43-14 | D00159B | | | FC | SP00489 | | 9 | | 002 |
| 5101B | 24 | | 7K | AN | 34-0 | 34-43-11 | D41061P | 4 | | | TB0150X | B001 | BJ | | 001-099 |
| 5101B | 24 | | 7K | AN | 32-5 | 34-43-11 | D41061P | 4 | | | TB0150F | C001 | 2 | | 115-199 |
| 5101W | 24 | | 7K | AN | 0-0 | 34-43-11 | D41061P | 3 | | | TB0150X | A001 | BJ | | 001-099 |
| 5101W | 24 | | 7K | AN | 0-0 | 34-43-11 | D41061P | 3 | | | TB0150F | A001 | 2 | | 115-199 |
| 5101Z | | | | AN | 0-0 | 34-43-11 | D41061P | 5 | | | GD00100 | ST.. | 2 | | ALL |
| 5102B | 24 | | 7K | AO | 0-9 | 34-43-11 | D00159B | D03 | | | TB0150X | B001 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2300

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2309 | 286N2309 | | | WEATHER RADAR-LEFT (continued) | | | | | | | | | | | |
| 5102B | 24 | 7K | AO | | 1-2 | 34-43-11 | D00159B | | D03 | | TB0150F | C001 | 2 | | 115-199 |
| 5102W | 24 | 7K | AO | | 0-0 | 34-43-11 | D00159B | | D02 | | TB0150X | A001 | BJ | | 001-099 |
| 5102W | 24 | 7K | AO | | 0-0 | 34-43-11 | D00159B | | D02 | | TB0150F | A001 | 2 | | 115-199 |
| 5102Z | | | AO | | 0-0 | 34-43-11 | D00159B | | DED | | GD00100 | ST.. | 2 | | ALL |
| 5103B | 24 | 7K | AP | | 35-0 | 34-43-11 | D41063P | | 2 | | TB0150X | B002 | BJ | | 001-099 |
| 5103B | 24 | 7K | AP | | 33-3 | 34-43-11 | D41063P | | 2 | | TB0150F | C002 | 2 | | 115-199 |
| 5103W | 24 | 7K | AP | | 0-0 | 34-43-11 | D41063P | | 1 | | TB0150X | A002 | BJ | | 001-099 |
| 5103W | 24 | 7K | AP | | 0-0 | 34-43-11 | D41063P | | 1 | | TB0150F | A002 | 2 | | 115-199 |
| 5103Z | | | AP | | 0-0 | 34-43-11 | D41063P | | 3 | | GD00100 | ST.. | 2 | | ALL |
| 5104B | 24 | 7K | AQ | | 0-9 | 34-43-11 | D00159B | | G03 | | TB0150X | B002 | BJ | | 001-099 |
| 5104B | 24 | 7K | AQ | | 1-2 | 34-43-11 | D00159B | | G03 | | TB0150F | C002 | 2 | | 115-199 |
| 5104W | 24 | 7K | AQ | | 0-0 | 34-43-11 | D00159B | | G02 | | TB0150X | A002 | BJ | | 001-099 |
| 5104W | 24 | 7K | AQ | | 0-0 | 34-43-11 | D00159B | | G02 | | TB0150F | A002 | 2 | | 115-199 |
| 5104Z | | | AQ | | 0-0 | 34-43-11 | D00159B | | DED | | GD00100 | ST.. | 2 | | ALL |
| 5105B | 24 | G2 | AR | | 35-0 | 34-43-11 | D41063P | | 5 | | D00159B | G13 | | | 001-099 |
| 5105B | 24 | G2 | AR | | 33-2 | 34-43-11 | D41063P | | 5 | | D00159B | G13 | | | 115-199 |
| 5105R | 24 | G2 | AR | | 0-0 | 34-43-11 | D41063P | | 4 | | D00159B | G12 | | | ALL |
| 5105Z | | | AR | | 0-0 | 34-43-11 | D41063P | | 6 | | GD02749 | ST.. | 2 | | ALL |
| 5106B | 24 | G2 | AS | | 35-0 | 34-43-11 | D41063P | | 8 | | D00159B | J12 | | | 001-099 |
| 5106B | 24 | G2 | AS | | 33-2 | 34-43-11 | D41063P | | 8 | | D00159B | J12 | | | 115-199 |
| 5106R | 24 | G2 | AS | | 0-0 | 34-43-11 | D41063P | | 7 | | D00159B | J11 | | | ALL |
| 5106Z | | | AS | | 0-0 | 34-43-11 | D41063P | | 9 | | GD02749 | ST.. | 2 | | ALL |
| 5107B | 22 | GU | AX | | 65-0 | 34-43-15 | D41238P | | 21 | | D00159B | J06 | | | 002 |
| 5107R | 22 | GU | AX | | 0-0 | 34-43-15 | D41238P | | 20 | | D00159B | J05 | | | 002 |
| 5107Z | | | AX | | 0-0 | 34-43-15 | D41238P | | 19 | | D00159B | | | FD | 002 |
| 8000 | 20 | GA | | | 1-6 | 34-43-15 | D00159B | | | FD | GD02749 | ST.. | 2 | | 002 |
| 8001 | 20 | GA | | | 1-6 | 34-43-14 | D00159B | | | FB | GD02749 | ST.. | 2 | | 002 |
| 8002 | 20 | GA | | | 1-6 | 34-43-14 | D00159B | | | FA | GD02749 | ST.. | 2 | | 002 |
| 8003 | 20 | GA | | | 1-6 | 34-43-14 | D00159B | | | FC | GD02749 | ST.. | 2 | | 002 |
| FRAA | | | | | 0-0 | 34-43-12 | D00159B | | | AA | GD02749 | ST.. | 2 | | ALL |
| FRAB | | | | | 0-0 | 34-43-12 | D00159B | | | AB | GD02749 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11
Section W2300
Page 6 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2311 | 286N2311 | | | LEFT EICAS DISP. UNIT-N10013 | | | | | | | | | | | |
| 0001 | 22 | GA | | | 11-0 | 31-41-11 | D00325 | | | 6 | TB0013X | A029 | BJ | | ALL |
| 0002 | 22 | GA | | | 11-0 | 31-41-11 | D00325 | | | 7 | GD01018 | AC.. | 2 | | 001-099 |
| 0002 | 22 | GA | | | 12-0 | 31-41-11 | D00325 | | | 7 | GD01018 | AC.. | 2 | | 115-199 |
| 0003 | 22 | GA | | | 11-0 | 31-41-11 | D00325 | | | 17 | GD01018 | ST.. | 2 | | 001-099 |
| 0003 | 22 | GA | | | 12-0 | 31-41-11 | D00325 | | | 17 | GD01018 | ST.. | 2 | | 115-199 |
| 0004 | 24 | GK | | | 11-0 | 31-41-19 | D00325 | | | 30 | TB0013X | C016 | BJ | | ALL |
| 0005 | 24 | GK | | | 11-0 | 31-41-19 | D00325 | | | 31 | TB0013X | D015 | BJ | | ALL |
| 0006 | 24 | GK | | | 11-0 | 31-41-19 | D00325 | | | 32 | TB0013X | D016 | BJ | | ALL |
| 0007 | 24 | GK | | | 10-0 | 31-41-19 | D00325 | | | 26 | TB0016X | D006 | BJ | | ALL |
| 0008 | 24 | GK | | | 10-0 | 31-41-19 | D00325 | | | 27 | TB0016X | C006 | BJ | | ALL |
| 0009 | 24 | GK | | | 10-0 | 31-41-19 | D00325 | | | 12 | TB0016X | B006 | BJ | | ALL |
| 0010 | 24 | GK | | | 10-0 | 31-41-19 | D00325 | | | 13 | TB0016X | A006 | BJ | | ALL |
| 0011 | 24 | GK | | | 55-0 | 31-41-14 | D41069P | | | 28 | D00325 | 22 | | | ALL |
| 0012 | 24 | GK | | | 55-0 | 31-41-14 | D41069P | | | 29 | D00325 | 23 | | | ALL |
| 0013 | 24 | GK | | | 55-0 | 31-41-14 | D41069P | | | 30 | D00325 | 24 | | | ALL |
| 0014 | 22 | GA | | | 11-0 | 31-41-11 | D00325 | | | 41 | TB0013Y | A007 | BJ | | ALL |
| 2501T | 24 | BV | AA | | 55-0 | 31-41-11 | D41069P | | | 2 | D00325 | 49 | | | ALL |
| 2501W | 24 | BV | AA | | 0-0 | 31-41-11 | D41069P | | | 3 | D00325 | 50 | | | ALL |
| 2501Z | | | AA | | 0-0 | 31-41-11 | D41069P | | | 1 | GD00225 | ST.. | 2 | | ALL |
| 2502T | 24 | BV | AB | | 55-0 | 31-41-11 | D41069P | | | 5 | D00325 | 51 | | | ALL |
| 2502W | 24 | BV | AB | | 0-0 | 31-41-11 | D41069P | | | 6 | D00325 | 52 | | | ALL |
| 2502Z | | | AB | | 0-0 | 31-41-11 | D41069P | | | 4 | GD00225 | ST.. | 2 | | ALL |
| 2503T | 24 | BV | AC | | 55-0 | 31-41-11 | D41069P | | | 8 | D00325 | 53 | | | ALL |
| 2503W | 24 | BV | AC | | 0-0 | 31-41-11 | D41069P | | | 9 | D00325 | 54 | | | ALL |
| 2503Z | | | AC | | 0-0 | 31-41-11 | D41069P | | | 7 | GD00225 | ST.. | 2 | | ALL |
| 2504T | 24 | BV | AD | | 55-0 | 31-41-11 | D41069P | | | 11 | D00325 | 63 | | | ALL |
| 2504W | 24 | BV | AD | | 0-0 | 31-41-11 | D41069P | | | 12 | D00325 | 64 | | | ALL |
| 2504Z | | | AD | | 0-0 | 31-41-11 | D41069P | | | 10 | GD00225 | ST.. | 2 | | ALL |
| 2505T | 24 | BV | AE | | 55-0 | 31-41-11 | D41069P | | | 14 | D00325 | 57 | | | ALL |
| 2505W | 24 | BV | AE | | 0-0 | 31-41-11 | D41069P | | | 15 | D00325 | 58 | | | ALL |
| 2505Z | | | AE | | 0-0 | 31-41-11 | D41069P | | | 13 | GD01855 | ST.. | 2 | | ALL |
| 2506T | 24 | BV | AF | | 55-0 | 31-41-11 | D41069P | | | 17 | D00325 | 62 | | | ALL |
| 2506W | 24 | BV | AF | | 0-0 | 31-41-11 | D41069P | | | 18 | D00325 | 61 | | | ALL |
| 2506Z | | | AF | | 0-0 | 31-41-11 | D41069P | | | 16 | GD01855 | ST.. | 2 | | ALL |
| 2507T | 24 | BV | AG | | 55-0 | 31-41-11 | D41069P | | | 20 | D00325 | 59 | | | ALL |
| 2507W | 24 | BV | AG | | 0-0 | 31-41-11 | D41069P | | | 21 | D00325 | 60 | | | ALL |
| 2507Z | | | AG | | 0-0 | 31-41-11 | D41069P | | | 19 | GD01855 | ST.. | 2 | | ALL |
| 2508T | 24 | BV | AH | | 55-0 | 31-41-11 | D41069P | | | 23 | D00325 | 55 | | | ALL |
| 2508W | 24 | BV | AH | | 0-0 | 31-41-11 | D41069P | | | 24 | D00325 | 56 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2310

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|-------------|------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice | |
| W2311 | 286N2311 | | | | LEFT EICAS DISP. UNIT-N10013 (continued) | | | | | | | | | | | |
| 2508Z | | | | AH | 0-0 | 31-41-11 | D41069P | 22 | | | GD01855 | ST.. | 2 | | ALL | |
| 2509T | 24 | BV | | AI | 55-0 | SPARE | D41069P | 25 | | | D00325 | CAP | Y | | 001-099 | |
| 2509W | 24 | BV | | AI | 0-0 | SPARE | D41069P | 26 | | | D00325 | CAP | Y | | 001-099 | |
| 2509Z | | | | AI | 0-0 | SPARE | D41069P | 27 | | | D00325 | DED | | | 001-099 | |
| 2510B | 24 | G2 | | AJ | 10-0 | 31-41-19 | D00325 | 29 | | | TB0016Z | 30 | BJ | | ALL | |
| 2510R | 24 | G2 | | AJ | 0-0 | 31-41-19 | D00325 | 28 | | | TB0016Z | 29 | BJ | | ALL | |
| 2510Z | | | | AJ | 0-0 | 31-41-19 | D00325 | DED | | | TB0016Z | 31 | BJ | | ALL | |
| W2313 | 286N2313 | | | | RIGHT EICAS DISP. UNIT-N10014 | | | | | | | | | | | |
| 0001 | 22 | GA | | | 10-0 | 31-41-21 | D00327 | 6 | | | TB0016X | D001 | BJ | | ALL | |
| 0002 | 22 | GA | | | 10-0 | 31-41-21 | D00327 | 7 | | | GD01247 | AC.. | 2 | | ALL | |
| 0003 | 22 | GA | | | 10-0 | 31-41-21 | D00327 | 17 | | | GD01247 | ST.. | 2 | | ALL | |
| 0004 | 24 | GK | | | 10-0 | 31-41-19 | D00327 | 30 | | | TB0016X | A001 | BJ | | ALL | |
| 0005 | 24 | GK | | | 10-0 | 31-41-19 | D00327 | 31 | | | TB0016X | B001 | BJ | | ALL | |
| 0006 | 24 | GK | | | 10-0 | 31-41-19 | D00327 | 32 | | | TB0016X | C001 | BJ | | ALL | |
| 0007 | 24 | GK | | | 10-0 | 31-41-19 | D00327 | 12 | | | TB0016X | D006 | BJ | | ALL | |
| 0008 | 24 | GK | | | 10-0 | 31-41-19 | D00327 | 13 | | | TB0016X | C006 | BJ | | ALL | |
| 0009 | 24 | GK | | | 10-0 | 31-41-19 | D00327 | 26 | | | TB0016X | B006 | BJ | | ALL | |
| 0010 | 24 | GK | | | 10-0 | 31-41-19 | D00327 | 27 | | | TB0016X | A006 | BJ | | ALL | |
| 0011 | 24 | GK | | | 46-0 | 31-41-14 | D41071P | 28 | | | D00327 | 22 | | | 001-099 | |
| 0011 | 24 | GK | | | 47-0 | 31-41-14 | D41071P | 28 | | | D00327 | 22 | | | 115-199 | |
| 0012 | 24 | GK | | | 46-0 | 31-41-14 | D41071P | 29 | | | D00327 | 23 | | | 001-099 | |
| 0012 | 24 | GK | | | 47-0 | 31-41-14 | D41071P | 29 | | | D00327 | 23 | | | 115-199 | |
| 0013 | 24 | GK | | | 46-0 | 31-41-14 | D41071P | 30 | | | D00327 | 24 | | | 001-099 | |
| 0013 | 24 | GK | | | 47-0 | 31-41-14 | D41071P | 30 | | | D00327 | 24 | | | 115-199 | |
| 0014 | 22 | GA | | | 10-0 | 31-41-21 | D00327 | 41 | | | TB0015Y | A007 | BJ | | ALL | |
| 2501T | 24 | BV | AA | | 46-0 | 31-41-21 | D41071P | 2 | | | D00327 | 49 | | | 001-099 | |
| 2501T | 24 | BV | AA | | 48-0 | 31-41-21 | D41071P | 2 | | | D00327 | 49 | | | 115-199 | |
| 2501W | 24 | BV | AA | | 0-0 | 31-41-21 | D41071P | 3 | | | D00327 | 50 | | | ALL | |
| 2501Z | | | | AA | 0-0 | 31-41-21 | D41071P | 1 | | | GD00261 | ST.. | 2 | | ALL | |
| 2502T | 24 | BV | AB | | 46-0 | 31-41-21 | D41071P | 5 | | | D00327 | 51 | | | 001-099 | |
| 2502T | 24 | BV | AB | | 48-0 | 31-41-21 | D41071P | 5 | | | D00327 | 51 | | | 115-199 | |
| 2502W | 24 | BV | AB | | 0-0 | 31-41-21 | D41071P | 6 | | | D00327 | 52 | | | ALL | |
| 2502Z | | | | AB | 0-0 | 31-41-21 | D41071P | 4 | | | GD00261 | ST.. | 2 | | ALL | |
| 2503T | 24 | BV | AC | | 46-0 | 31-41-21 | D41071P | 8 | | | D00327 | 53 | | | 001-099 | |
| 2503T | 24 | BV | AC | | 48-0 | 31-41-21 | D41071P | 8 | | | D00327 | 53 | | | 115-199 | |
| 2503W | 24 | BV | AC | | 0-0 | 31-41-21 | D41071P | 9 | | | D00327 | 54 | | | ALL | |
| 2503Z | | | | AC | 0-0 | 31-41-21 | D41071P | 7 | | | GD00261 | ST.. | 2 | | ALL | |
| 2504T | 24 | BV | AD | | 46-0 | 31-41-21 | D41071P | 11 | | | D00327 | 63 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2310

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2313 | 286N2313 | | | RIGHT EICAS DISP. UNIT-N10014 (continued) | | | | | | | | | | | |
| 2504T | 24 | BV | AD | | 48-0 | 31-41-21 | D41071P | | 11 | | D00327 | 63 | | | 115-199 |
| 2504W | 24 | BV | AD | | 0-0 | 31-41-21 | D41071P | | 12 | | D00327 | 64 | | | ALL |
| 2504Z | | | AD | | 0-0 | 31-41-21 | D41071P | | 10 | | GD00261 | ST.. | 2 | | ALL |
| 2505T | 24 | BV | AE | | 46-0 | 31-41-21 | D41071P | | 14 | | D00327 | 57 | | | 001-099 |
| 2505T | 24 | BV | AE | | 48-0 | 31-41-21 | D41071P | | 14 | | D00327 | 57 | | | 115-199 |
| 2505W | 24 | BV | AE | | 0-0 | 31-41-21 | D41071P | | 15 | | D00327 | 58 | | | ALL |
| 2505Z | | | AE | | 0-0 | 31-41-21 | D41071P | | 13 | | GD01995 | ST.. | 2 | | ALL |
| 2506T | 24 | BV | AF | | 46-0 | 31-41-21 | D41071P | | 17 | | D00327 | 62 | | | 001-099 |
| 2506T | 24 | BV | AF | | 48-0 | 31-41-21 | D41071P | | 17 | | D00327 | 62 | | | 115-199 |
| 2506W | 24 | BV | AF | | 0-0 | 31-41-21 | D41071P | | 18 | | D00327 | 61 | | | ALL |
| 2506Z | | | AF | | 0-0 | 31-41-21 | D41071P | | 16 | | GD01995 | ST.. | 2 | | ALL |
| 2507T | 24 | BV | AG | | 46-0 | 31-41-21 | D41071P | | 20 | | D00327 | 59 | | | 001-099 |
| 2507T | 24 | BV | AG | | 48-0 | 31-41-21 | D41071P | | 20 | | D00327 | 59 | | | 115-199 |
| 2507W | 24 | BV | AG | | 0-0 | 31-41-21 | D41071P | | 21 | | D00327 | 60 | | | ALL |
| 2507Z | | | AG | | 0-0 | 31-41-21 | D41071P | | 19 | | GD01995 | ST.. | 2 | | ALL |
| 2508T | 24 | BV | AH | | 46-0 | 31-41-21 | D41071P | | 23 | | D00327 | 55 | | | 001-099 |
| 2508T | 24 | BV | AH | | 48-0 | 31-41-21 | D41071P | | 23 | | D00327 | 55 | | | 115-199 |
| 2508W | 24 | BV | AH | | 0-0 | 31-41-21 | D41071P | | 24 | | D00327 | 56 | | | ALL |
| 2508Z | | | AH | | 0-0 | 31-41-21 | D41071P | | 22 | | GD01995 | ST.. | 2 | | ALL |
| 2509T | 24 | BV | AI | | 46-0 | SPARE | D41071P | | 25 | | D00327 | CAP | Y | | 001-099 |
| 2509W | 24 | BV | AI | | 0-0 | SPARE | D41071P | | 26 | | D00327 | CAP | Y | | 001-099 |
| 2509Z | | | AI | | 0-0 | SPARE | D41071P | | 27 | | D00327 | DED | | | 001-099 |
| 2510B | 24 | G2 | AJ | | 10-0 | 31-41-19 | D00327 | | 29 | | TB0016Z | 30 | BJ | | ALL |
| 2510R | 24 | G2 | AJ | | 0-0 | 31-41-19 | D00327 | | 28 | | TB0016Z | 29 | BJ | | ALL |
| 2510Z | | | AJ | | 0-0 | 31-41-19 | D00327 | DED | | | TB0016Z | 31 | BJ | | ALL |
| W2314 | 286N2314 | | | WINDOW HEAT-R WINDOW 1 | | | | | | | | | | | |
| A-AA | | | | | 0-0 | 30-41-12 | D03270 | = | 1 | | TB5038 | 1 | E | | ALL |
| A-AB | | | | | 0-0 | 30-41-12 | D03272 | = | 1 | | TB5038 | 1 | E | | ALL |
| A-AC | | | | | 0-0 | 30-41-12 | D03274 | = | 1 | | TB5038 | 2 | E | | ALL |
| A-BA | | | | | 0-0 | 30-41-12 | D03276 | | A | | TB5038 | 3 | E | | ALL |
| A-BB | | | | | 0-0 | 30-41-12 | D03276 | | B | | TB5038 | 4 | E | | ALL |
| A-CA | | | | | 0-0 | 30-41-12 | D03278 | | A | | TB5038 | 5 | E | | ALL |
| A-CB | | | | | 0-0 | 30-41-12 | D03278 | | B | | TB5038 | 6 | E | | ALL |
| W2315 | 286N2315 | | | EICAS D.S.P. #1(M10195) | | | | | | | | | | | |
| 0001 | 22 | GA | | | 9-0 | 31-41-19 | D00331 | | 38 | | TB0101X | C002 | BJ | | ALL |
| 0002 | 24 | GK | | | 10-0 | 31-41-19 | D00331 | | 39 | | GD02316 | AC.. | 2 | | ALL |
| 0004 | 24 | GK | | | 49-0 | 31-41-19 | D41065P | | 2 | | D00331 | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2310

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2315 | 286N2315 | | | | EICAS D.S.P. #1(M10195) (continued) | | | | | | | | | | | |
| 0005 | 24 | | GK | | 49-0 | 31-41-19 | | D41065P | | | | D00331 | 8 | | | ALL |
| 0006 | 24 | | GK | | 18-0 | 31-41-19 | | D00331 | | | | TB0016X | A001 | BJ | | ALL |
| 0007 | 24 | | GK | | 18-0 | 31-41-19 | | D00331 | | | | TB0016X | B001 | BJ | | ALL |
| 0008 | 24 | | GK | | 18-0 | 31-41-19 | | D00331 | | | | TB0016X | C001 | BJ | | ALL |
| 0009 | 24 | | GK | | 12-0 | 31-41-19 | | D00331 | | | | TB0014X | C005 | BJ | | ALL |
| 0010 | 24 | | GK | | 12-0 | 31-41-19 | | D00331 | | | | TB0014X | D005 | BJ | | ALL |
| 0011 | 24 | | GK | | 12-0 | 31-41-19 | | D00331 | | | | TB0013X | C016 | BJ | | ALL |
| 0012 | 24 | | GK | | 12-0 | 31-41-19 | | D00331 | | | | TB0013X | D015 | BJ | | ALL |
| 0013 | 24 | | GK | | 12-0 | 31-41-19 | | D00331 | | | | TB0013X | D016 | BJ | | ALL |
| 0014 | 24 | | GK | | 64-0 | 31-41-19 | | D41065P | | | | TB0121Z | 13 | BJ | | ALL |
| 0015 | 20 | | GA | | 9-0 | 33-13-52 | | D00331 | | | | TB0101Y | A003 | BJ | | ALL |
| 0016 | 20 | | GA | | 10-0 | 33-13-52 | | D00331 | | | | GD02316 | AC.. | 2 | | ALL |
| 0018 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 18 | | | ALL |
| 0019 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 16 | | | ALL |
| 0022 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 10 | | | ALL |
| 0023 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 12 | | | ALL |
| 0024 | 24 | | GK | | 10-0 | 31-41-19 | | D00331 | | | | GD02316 | DC.. | 2 | | ALL |
| 0025 | 24 | | GK | | 10-0 | 31-41-19 | | D00331 | | | | GD02316 | ST.. | 2 | | ALL |
| 0027 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 14 | | | ALL |
| 0029 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 24 | | | ALL |
| 0030 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 26 | | | ALL |
| 0031 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 28 | | | ALL |
| 0032 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 30 | | | ALL |
| 0033 | 24 | | GK | | 35-0 | 31-41-19 | | D00331 | | | | D00517 | 36 | | | ALL |
| 0036 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 12 | BJ | | ALL |
| 0040 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 13 | BJ | | ALL |
| 0041 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 13 | BJ | | ALL |
| 0042 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 13 | BJ | | ALL |
| 0043 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 14 | BJ | | ALL |
| 0044 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 14 | BJ | | ALL |
| 0045 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 14 | BJ | | ALL |
| 0047 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 12 | BJ | | ALL |
| 0048 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 12 | BJ | | ALL |
| 0049 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 13 | BJ | | ALL |
| 0053 | 24 | | GK | | 8-0 | 31-41-19 | | D00517 | | | | GD00618 | DC.. | 2 | | ALL |
| 0054 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 14 | BJ | | ALL |
| 0056 | 20 | | GA | | 1-0 | 31-41-19 | | TB0121Z | | BJ | | TB0121Z | 13 | BJ | | ALL |
| 0057 | 20 | | GA | | 1-0 | 31-41-19 | | TB0121Z | | BJ | | TB0121Z | 14 | BJ | | ALL |
| 0559 | 24 | | GK | | 9-0 | 31-41-19 | | D00517 | | | | TB0121Z | 14 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2310

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2315 | 286N2315 | | | EICAS D.S.P. #1(M10195) (continued) | | | | | | | | | | | |
| 5001B | 24 | | G2 | AA | 50-0 | 31-41-19 | D41065P | 11 | | | D00331 | 20 | | | 001-099 |
| 5001B | 24 | | G2 | AA | 49-0 | 31-41-19 | D41065P | 11 | | | D00331 | 20 | | | 115-199 |
| 5001R | 24 | | G2 | AA | 0-0 | 31-41-19 | D41065P | 10 | | | D00331 | 19 | | | ALL |
| 5001Z | | | | AA | 0-0 | 31-41-19 | D41065P | 12 | | | GD01400 | ST.. | E | | ALL |
| 5002B | 24 | | G2 | AB | 50-0 | 31-41-19 | D41065P | 9 | | | D00331 | 18 | | | 001-099 |
| 5002B | 24 | | G2 | AB | 49-0 | 31-41-19 | D41065P | 9 | | | D00331 | 18 | | | 115-199 |
| 5002R | 24 | | G2 | AB | 0-0 | 31-41-19 | D41065P | 8 | | | D00331 | 17 | | | ALL |
| 5002Z | | | | AB | 0-0 | 31-41-19 | D41065P | 7 | | | GD01400 | ST.. | E | | ALL |
| W2316 | 286N2316 | | | WINDOW HEAT-R WINDOW 2 | | | | | | | | | | | |
| A-AA | | | | | 0-0 | 30-41-11 | D03284 | | A | | D41576J | 4 | | | ALL |
| A-AB | | | | | 0-0 | 30-41-11 | D03284 | | B | | D41576J | 5 | | | ALL |
| A-BA | | | | | 0-0 | 30-41-11 | D03282 | | A | | D41576J | 2 | | | ALL |
| A-BB | | | | | 0-0 | 30-41-11 | D03282 | | B | | D41576J | 3 | | | ALL |
| A-CA | | | | | 0-0 | 30-41-11 | D03280 | | C | | D41576J | 1 | | | ALL |
| A-CB | | | | | 0-0 | 30-41-11 | D03280 | | D | | D41576J | 6 | | | ALL |
| W2318 | 286N2318 | | | WINDOW HEAT-R WINDOW 3 | | | | | | | | | | | |
| A-DA | | | | | 0-0 | 30-41-11 | D03286 | | = 1 | | TB5040 | 1 | C | | ALL |
| A-DB | | | | | 0-0 | 30-41-11 | D04680 | | = 1 | | TB5040 | 2 | C | | ALL |
| A-EA | | | | | 0-0 | 30-41-11 | D03288 | | A | | TB5040 | 3 | C | | ALL |
| A-EB | | | | | 0-0 | 30-41-11 | D03288 | | B | | TB5040 | 4 | C | | ALL |
| A-FA | | | | | 0-0 | 30-41-11 | D03290 | | A | | TB5040 | 5 | C | | ALL |
| A-FB | | | | | 0-0 | 30-41-11 | D03290 | | B | | TB5040 | 6 | C | | ALL |

WIRE LIST

D280N032

91-21-11
Section W2310
Page 5 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2321 | 286N2321 | | | EFIS DISP. UNITS-CAPT. | | | | | | | | | | | |
| 0001 | 24 | | GK | | 14-0 | 34-22-15 | D00089 | | 67 | | D00095 | 23 | | | 001-099 |
| 0001 | 24 | | GK | | 13-0 | 34-22-15 | D00089 | | 67 | | D00095 | 23 | | | 115-199 |
| 0002 | 24 | | GK | | 34-0 | 34-22-15 | D00089 | | 22 | | D41075P | 28 | | | ALL |
| 0003 | 24 | | GK | | 34-0 | 34-22-15 | D00089 | | 23 | | D41075P | 29 | | | ALL |
| 0004 | 24 | | GK | | 34-0 | 34-22-15 | D00089 | | 24 | | D41075P | 30 | | | ALL |
| 0005 | 24 | | GK | | 8-0 | 34-22-15 | D00089 | | 1 | | TB0014X | A001 | BJ | | ALL |
| 0006 | 24 | | GK | | 8-0 | 34-22-15 | D00089 | | 2 | | TB0014X | B001 | BJ | | ALL |
| 0007 | 24 | | GK | | 8-0 | 34-22-15 | D00089 | | 8 | | TB0014X | C001 | BJ | | ALL |
| 0008 | 24 | | GK | | 14-0 | 34-22-14 | D00087 | | 67 | | D00095 | 24 | | | 001-099 |
| 0008 | 24 | | GK | | 13-0 | 34-22-14 | D00087 | | 67 | | D00095 | 24 | | | 115-199 |
| 0009 | 24 | | GK | | 34-0 | 34-22-14 | D00087 | | 22 | | D41073P | 28 | | | ALL |
| 0010 | 24 | | GK | | 34-0 | 34-22-14 | D00087 | | 23 | | D41073P | 29 | | | ALL |
| 0011 | 24 | | GK | | 34-0 | 34-22-14 | D00087 | | 24 | | D41073P | 30 | | | ALL |
| 0012 | 22 | | GA | | 8-0 | 34-22-16 | D00087 | | 17 | | GD01018 | ST.. | 2 | | ALL |
| 0013 | 22 | | GA | | 8-0 | 34-22-16 | D00087 | | 7 | | GD01018 | AC.. | 2 | | ALL |
| 0014 | 24 | | GK | | 8-0 | 34-22-16 | D00087 | | 6 | | TB0014X | A002 | BJ | | ALL |
| 0015 | 24 | | GK | | 8-0 | 34-22-16 | D00089 | | 6 | | TB0014X | D002 | BJ | | ALL |
| 0016 | 22 | | GA | | 8-0 | 34-22-16 | D00089 | | 7 | | GD01018 | AC.. | 2 | | ALL |
| 0017 | 22 | | GA | | 8-0 | 34-22-16 | D00089 | | 17 | | GD01018 | ST.. | 2 | | ALL |
| 0018 | 24 | | GK | | 6-0 | 34-22-16 | D00095 | | 3 | | TB0101X | C001 | BJ | | ALL |
| 0019 | 20 | | GA | | 3-0 | 34-22-16 | D00095 | | 4 | | GD01603 | AC.. | 2 | | ALL |
| 0020 | 20 | | GA | | 3-0 | 34-22-16 | D00095 | | 34 | | GD01601 | DC.. | 2 | | ALL |
| 0021 | 20 | | GA | | 3-0 | 34-22-16 | D00095 | | 5 | | GD01601 | DC.. | 2 | | ALL |
| 0022 | 20 | | GA | | 3-0 | 34-22-16 | D00095 | | 38 | | GD01601 | DC.. | 2 | | ALL |
| 0023 | 24 | | GK | | 34-0 | 34-43-12 | D00095 | | 14 | | D41073P | 34 | | | 001-099 |
| 0023 | 24 | | GK | | 33-0 | 34-43-12 | D00095 | | 14 | | D41073P | 34 | | | 115-199 |
| 0024 | 24 | | GK | | 13-0 | 34-22-18 | D00095 | | 21 | | TB0013Z | 27 | BJ | | 001-099 |
| 0024 | 24 | | GK | | 12-0 | 34-22-18 | D00095 | | 21 | | TB0013Z | 27 | BJ | | 115-199 |
| 0025 | 24 | | GK | | 13-0 | 34-22-18 | D00095 | | 17 | | TB0013Z | 27 | BJ | | 001-099 |
| 0025 | 24 | | GK | | 12-0 | 34-22-18 | D00095 | | 17 | | TB0013Z | 27 | BJ | | 115-199 |
| 0026 | 24 | | GK | | 13-0 | 34-22-18 | D00095 | | 20 | | TB0013Y | A011 | BJ | | 001-099 |
| 0026 | 24 | | GK | | 12-0 | 34-22-18 | D00095 | | 20 | | TB0013Y | A011 | BJ | | 115-199 |
| 0027 | 24 | | GK | | 13-0 | 34-22-18 | D00095 | | 18 | | TB0013Y | A011 | BJ | | 001-099 |
| 0027 | 24 | | GK | | 12-0 | 34-22-18 | D00095 | | 18 | | TB0013Y | A011 | BJ | | 115-199 |
| 0028 | 22 | | GA | | 3-0 | 34-22-18 | D00095 | | 16 | | GD01601 | DC.. | 2 | | ALL |
| 0029 | 24 | | GK | | 8-0 | 34-22-15 | D00089 | | 41 | | TB0013Y | A007 | BJ | | ALL |
| 0031 | 20 | | GA | | 6-0 | 33-13-52 | D00095 | | 1 | | TB0101Z | 9 | BJ | | ALL |
| 0032 | 20 | | GA | | 3-0 | 33-13-52 | D00095 | | 2 | | GD01603 | AC.. | 2 | | ALL |
| 0035 | 24 | | GK | | 8-0 | 34-22-14 | D00087 | | 41 | | TB0013Y | A007 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2320

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|------------------------------------|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W2321 | 286N2321 | | | EFIS DISP. UNITS-CAPT. (continued) | | | | | | | | | | | | |
| 0036 | 24 | | GK | | 34-0 | 34-22-16 | D41073P | 35 | | | | TB0013X | D029 | BJ | | 001-099 |
| 0036 | 24 | | GK | | 33-0 | 34-22-16 | D41073P | 35 | | | | TB0013X | C030 | BJ | | 115-199 |
| 0037 | 20 | | GA | | 3-0 | 34-22-16 | D00095 | 39 | | | | GD01601 | DC.. | 2 | | 115-199 |
| 0038 | 24 | | GK | | 34-0 | 34-22-16 | TB0013X | A030 | BJ | | | D41073P | 36 | | | 001-099 |
| 0038 | 24 | | GK | | 33-0 | 34-22-16 | TB0013X | A030 | BJ | | | D41073P | 36 | | | 115-199 |
| 0039 | 24 | | GK | | 34-0 | 34-22-16 | TB0013X | B030 | BJ | | | D41073P | 37 | | | 001-099 |
| 0039 | 24 | | GK | | 33-0 | 34-22-16 | TB0013X | B030 | BJ | | | D41073P | 37 | | | 115-199 |
| 2001B | 24 | | GL | AB | 6-0 | 34-22-14 | D00087 | 27 | | | | D00089 | 13 | | | 001-099 |
| 2001B | 24 | | GL | AB | 7-0 | 34-22-14 | D00087 | 27 | | | | D00089 | 13 | | | 115-199 |
| 2001R | 24 | | GL | AB | 0-0 | 34-22-14 | D00087 | 26 | | | | D00089 | 12 | | | ALL |
| 2002B | 24 | | GL | AA | 6-0 | 34-22-14 | D00087 | 13 | | | | D00089 | 27 | | | ALL |
| 2002R | 24 | | GL | AA | 0-0 | 34-22-14 | D00087 | 12 | | | | D00089 | 26 | | | ALL |
| 2501T | 24 | | BV | AN | 34-0 | 34-22-15 | D41075P | 1 | | | | D00089 | 49 | | | ALL |
| 2501W | 24 | | BV | AN | 0-0 | 34-22-15 | D41075P | 2 | | | | D00089 | 50 | | | ALL |
| 2501Z | | | | AN | 0-0 | 34-22-15 | D41075P | 3 | | | | GD02093 | ST.. | 2 | | ALL |
| 2502T | 24 | | BV | AO | 34-0 | 34-22-15 | D41075P | 4 | | | | D00089 | 51 | | | ALL |
| 2502W | 24 | | BV | AO | 0-0 | 34-22-15 | D41075P | 5 | | | | D00089 | 52 | | | ALL |
| 2502Z | | | | AO | 0-0 | 34-22-15 | D41075P | 6 | | | | GD02093 | ST.. | 2 | | ALL |
| 2503T | 24 | | BV | AP | 34-0 | 34-22-15 | D41075P | 7 | | | | D00089 | 53 | | | ALL |
| 2503W | 24 | | BV | AP | 0-0 | 34-22-15 | D41075P | 8 | | | | D00089 | 54 | | | ALL |
| 2503Z | | | | AP | 0-0 | 34-22-15 | D41075P | 9 | | | | GD02093 | ST.. | 2 | | ALL |
| 2504T | 24 | | BV | AQ | 34-0 | 34-22-15 | D41075P | 10 | | | | D00089 | 55 | | | ALL |
| 2504W | 24 | | BV | AQ | 0-0 | 34-22-15 | D41075P | 11 | | | | D00089 | 56 | | | ALL |
| 2504Z | | | | AQ | 0-0 | 34-22-15 | D41075P | 12 | | | | GD00739 | ST.. | 2 | | ALL |
| 2505T | 24 | | BV | AR | 34-0 | 34-22-15 | D41075P | 13 | | | | D00089 | 57 | | | ALL |
| 2505W | 24 | | BV | AR | 0-0 | 34-22-15 | D41075P | 14 | | | | D00089 | 58 | | | ALL |
| 2505Z | | | | AR | 0-0 | 34-22-15 | D41075P | 15 | | | | GD00739 | ST.. | 2 | | ALL |
| 2506T | 24 | | BV | AS | 34-0 | 34-22-15 | D41075P | 16 | | | | D00089 | 59 | | | ALL |
| 2506W | 24 | | BV | AS | 0-0 | 34-22-15 | D41075P | 17 | | | | D00089 | 60 | | | ALL |
| 2506Z | | | | AS | 0-0 | 34-22-15 | D41075P | 18 | | | | GD00739 | ST.. | 2 | | ALL |
| 2507T | 24 | | BV | AT | 34-0 | 34-22-15 | D41075P | 19 | | | | D00089 | 61 | | | ALL |
| 2507W | 24 | | BV | AT | 0-0 | 34-22-15 | D41075P | 20 | | | | D00089 | 62 | | | ALL |
| 2507Z | | | | AT | 0-0 | 34-22-15 | D41075P | 21 | | | | GD00739 | ST.. | 2 | | ALL |
| 2508T | 24 | | BV | AU | 34-0 | 34-22-15 | D41075P | 22 | | | | D00089 | 63 | | | ALL |
| 2508W | 24 | | BV | AU | 0-0 | 34-22-15 | D41075P | 23 | | | | D00089 | 64 | | | ALL |
| 2508Z | | | | AU | 0-0 | 34-22-15 | D41075P | 24 | | | | GD00739 | ST.. | 2 | | ALL |
| 2509T | 24 | | BV | AV | 34-0 | 34-22-15 | D41075P | 25 | | | | D00089 | 65 | | | ALL |
| 2509W | 24 | | BV | AV | 0-0 | 34-22-15 | D41075P | 26 | | | | D00089 | 66 | | | ALL |
| 2509Z | | | | AV | 0-0 | 34-22-15 | D41075P | 27 | | | | GD00739 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2320

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2321 | 286N2321 | | | EFIS DISP. UNITS-CAPT. (continued) | | | | | | | | | | | |
| 2510B | 24 | G2 | AD | | 8-0 | 34-22-15 | D00089 | 29 | | | TB0014Y | C021 | BJ | | 001-099 |
| 2510B | 24 | G2 | AD | | 6-0 | 34-22-15 | D00089 | 29 | | | TB0014Y | C021 | BJ | | 115-199 |
| 2510R | 24 | G2 | AD | | 0-0 | 34-22-15 | D00089 | 28 | | | TB0014Y | A021 | BJ | | ALL |
| 2510Z | | | AD | | 0-0 | 34-22-15 | GD00739 | ST.. | 2 | | TB0014Y | A020 | BJ | | ALL |
| 2511B | 24 | G2 | AC | | 8-0 | 34-22-14 | D00087 | 29 | | | TB0014Y | C021 | BJ | | 001-099 |
| 2511B | 24 | G2 | AC | | 6-0 | 34-22-14 | D00087 | 29 | | | TB0014Y | C021 | BJ | | 115-199 |
| 2511R | 24 | G2 | AC | | 0-0 | 34-22-14 | D00087 | 28 | | | TB0014Y | A021 | BJ | | ALL |
| 2511Z | | | AC | | 0-0 | 34-22-14 | GD01053 | ST.. | 2 | | TB0014Y | A020 | BJ | | ALL |
| 2512T | 24 | BV | AE | | 34-0 | 34-22-14 | D41073P | 1 | | | D00087 | 49 | | | ALL |
| 2512W | 24 | BV | AE | | 0-0 | 34-22-14 | D41073P | 2 | | | D00087 | 50 | | | ALL |
| 2512Z | | | AE | | 0-0 | 34-22-14 | D41073P | 3 | | | GD01053 | ST.. | 2 | | ALL |
| 2513T | 24 | BV | AF | | 34-0 | 34-22-14 | D41073P | 4 | | | D00087 | 51 | | | ALL |
| 2513W | 24 | BV | AF | | 0-0 | 34-22-14 | D41073P | 5 | | | D00087 | 52 | | | ALL |
| 2513Z | | | AF | | 0-0 | 34-22-14 | D41073P | 6 | | | GD01053 | ST.. | 2 | | ALL |
| 2514T | 24 | BV | AG | | 34-0 | 34-22-14 | D41073P | 7 | | | D00087 | 53 | | | ALL |
| 2514W | 24 | BV | AG | | 0-0 | 34-22-14 | D41073P | 8 | | | D00087 | 54 | | | ALL |
| 2514Z | | | AG | | 0-0 | 34-22-14 | D41073P | 9 | | | GD01053 | ST.. | 2 | | ALL |
| 2515T | 24 | BV | AH | | 34-0 | 34-22-14 | D41073P | 10 | | | D00087 | 55 | | | ALL |
| 2515W | 24 | BV | AH | | 0-0 | 34-22-14 | D41073P | 11 | | | D00087 | 56 | | | ALL |
| 2515Z | | | AH | | 0-0 | 34-22-14 | D41073P | 12 | | | GD01053 | ST.. | 2 | | ALL |
| 2516T | 24 | BV | AI | | 34-0 | 34-22-14 | D41073P | 13 | | | D00087 | 57 | | | ALL |
| 2516W | 24 | BV | AI | | 0-0 | 34-22-14 | D41073P | 14 | | | D00087 | 58 | | | ALL |
| 2516Z | | | AI | | 0-0 | 34-22-14 | D41073P | 15 | | | GD01053 | ST.. | 2 | | ALL |
| 2517T | 24 | BV | AJ | | 34-0 | 34-22-14 | D41073P | 16 | | | D00087 | 59 | | | ALL |
| 2517W | 24 | BV | AJ | | 0-0 | 34-22-14 | D41073P | 17 | | | D00087 | 60 | | | ALL |
| 2517Z | | | AJ | | 0-0 | 34-22-14 | D41073P | 18 | | | GD01053 | ST.. | 2 | | ALL |
| 2518T | 24 | BV | AK | | 34-0 | 34-22-14 | D41073P | 19 | | | D00087 | 61 | | | ALL |
| 2518W | 24 | BV | AK | | 0-0 | 34-22-14 | D41073P | 20 | | | D00087 | 62 | | | ALL |
| 2518Z | | | AK | | 0-0 | 34-22-14 | D41073P | 21 | | | GD02399 | ST.. | 2 | | ALL |
| 2519T | 24 | BV | AL | | 34-0 | 34-22-14 | D41073P | 22 | | | D00087 | 63 | | | ALL |
| 2519W | 24 | BV | AL | | 0-0 | 34-22-14 | D41073P | 23 | | | D00087 | 64 | | | ALL |
| 2519Z | | | AL | | 0-0 | 34-22-14 | D41073P | 24 | | | GD02399 | ST.. | 2 | | ALL |
| 2520T | 24 | BV | AM | | 34-0 | 34-22-14 | D41073P | 25 | | | D00087 | 65 | | | ALL |
| 2520W | 24 | BV | AM | | 0-0 | 34-22-14 | D41073P | 26 | | | D00087 | 66 | | | ALL |
| 2520Z | | | AM | | 0-0 | 34-22-14 | D41073P | 27 | | | GD02399 | ST.. | 2 | | ALL |
| 3001B | 24 | GM | AY | | 14-0 | 34-22-15 | D00089 | 34 | | | D00095 | 29 | | | 001-099 |
| 3001B | 24 | GM | AY | | 13-0 | 34-22-15 | D00089 | 34 | | | D00095 | 29 | | | 115-199 |
| 3001R | 24 | GM | AY | | 0-0 | 34-22-15 | D00089 | 33 | | | D00095 | 30 | | | ALL |
| 3001Y | 24 | GM | AY | | 0-0 | 34-22-15 | D00089 | 35 | | | D00095 | 28 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2320

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2321 | 286N2321 | | | EFIS DISP. UNITS-CAPT. (continued) | | | | | | | | | | | |
| 3002B | 24 | | GM | AZ | 14-0 | 34-22-15 | D00089 | 31 | | | D00095 | 26 | | | 001-099 |
| 3002B | 24 | | GM | AZ | 13-0 | 34-22-15 | D00089 | 31 | | | D00095 | 26 | | | 115-199 |
| 3002R | 24 | | GM | AZ | 0-0 | 34-22-15 | D00089 | 30 | | | D00095 | 27 | | | ALL |
| 3002Y | 24 | | GM | AZ | 0-0 | 34-22-15 | D00089 | 32 | | | D00095 | 25 | | | ALL |
| 3003B | 24 | | GM | AX | 14-0 | 34-22-14 | D00087 | 31 | | | D00095 | 32 | | | 001-099 |
| 3003B | 24 | | GM | AX | 13-0 | 34-22-14 | D00087 | 31 | | | D00095 | 32 | | | 115-199 |
| 3003R | 24 | | GM | AX | 0-0 | 34-22-14 | D00087 | 30 | | | D00095 | 33 | | | ALL |
| 3003Y | 24 | | GM | AX | 0-0 | 34-22-14 | D00087 | 32 | | | D00095 | 31 | | | ALL |
| 5001B | 24 | | G2 | AW | 34-0 | 34-22-14 | D00095 | 35 | | | D41073P | 31 | | | 001-099 |
| 5001B | 24 | | G2 | AW | 33-0 | 34-22-14 | D00095 | 35 | | | D41073P | 31 | | | 115-199 |
| 5001R | 24 | | G2 | AW | 0-0 | 34-22-14 | D00095 | 36 | | | D41073P | 32 | | | ALL |
| 5001Z | | | | AW | 0-0 | 34-22-14 | D41073P | 33 | | | GD01644 | ST.. | E | | ALL |
| W2323 | 286N2323 | | | EFIS DISP. UNITS-F/O | | | | | | | | | | | |
| 0001 | 24 | | GK | | 33-0 | 34-22-24 | D00091 | 22 | | | D41077P | 28 | | | ALL |
| 0002 | 24 | | GK | | 33-0 | 34-22-24 | D00091 | 23 | | | D41077P | 29 | | | ALL |
| 0003 | 24 | | GK | | 33-0 | 34-22-24 | D00091 | 24 | | | D41077P | 30 | | | ALL |
| 0004 | 24 | | GK | | 13-0 | 34-22-24 | D00091 | 67 | | | D00097 | 24 | | | 001-099 |
| 0004 | 24 | | GK | | 14-0 | 34-22-24 | D00091 | 67 | | | D00097 | 24 | | | 115-199 |
| 0005 | 22 | | GA | | 7-0 | 34-22-26 | D00091 | 17 | | | GD01247 | ST.. | 2 | | 001-099 |
| 0005 | 22 | | GA | | 6-0 | 34-22-26 | D00091 | 17 | | | GD01247 | ST.. | 2 | | 115-199 |
| 0006 | 22 | | GA | | 7-0 | 34-22-26 | D00091 | 7 | | | GD01247 | AC.. | 2 | | 001-099 |
| 0006 | 22 | | GA | | 6-0 | 34-22-26 | D00091 | 7 | | | GD01247 | AC.. | 2 | | 115-199 |
| 0007 | 24 | | GK | | 7-0 | 34-22-26 | D00091 | 6 | | | TB0016X | A002 | BJ | | 001-099 |
| 0007 | 24 | | GK | | 6-0 | 34-22-26 | D00091 | 6 | | | TB0016X | A002 | BJ | | 115-199 |
| 0008 | 24 | | GK | | 7-0 | 34-22-26 | D00093 | 6 | | | TB0016X | B002 | BJ | | 001-099 |
| 0008 | 24 | | GK | | 6-0 | 34-22-26 | D00093 | 6 | | | TB0016X | B002 | BJ | | 115-199 |
| 0009 | 22 | | GA | | 7-0 | 34-22-26 | D00093 | 7 | | | GD01247 | AC.. | 2 | | 001-099 |
| 0009 | 22 | | GA | | 6-0 | 34-22-26 | D00093 | 7 | | | GD01247 | AC.. | 2 | | 115-199 |
| 0010 | 22 | | GA | | 7-0 | 34-22-26 | D00093 | 17 | | | GD01247 | ST.. | 2 | | 001-099 |
| 0010 | 22 | | GA | | 6-0 | 34-22-26 | D00093 | 17 | | | GD01247 | ST.. | 2 | | 115-199 |
| 0011 | 24 | | GK | | 6-0 | 34-22-26 | D00097 | 3 | | | TB0100X | C001 | BJ | | 001-099 |
| 0011 | 24 | | GK | | 7-0 | 34-22-26 | D00097 | 3 | | | TB0100X | C001 | BJ | | 115-199 |
| 0012 | 20 | | GA | | 4-0 | 34-22-26 | D00097 | 4 | | | GD01604 | AC.. | 2 | | 001-099 |
| 0012 | 20 | | GA | | 7-0 | 34-22-26 | D00097 | 4 | | | GD01604 | AC.. | 2 | | 115-199 |
| 0013 | 20 | | GA | | 4-0 | 34-22-26 | D00097 | 34 | | | GD01602 | DC.. | 2 | | 001-099 |
| 0013 | 20 | | GA | | 7-0 | 34-22-26 | D00097 | 34 | | | GD01602 | DC.. | 2 | | 115-199 |
| 0014 | 20 | | GA | | 4-0 | 34-22-26 | D00097 | 5 | | | GD01602 | DC.. | 2 | | 001-099 |
| 0014 | 20 | | GA | | 7-0 | 34-22-26 | D00097 | 5 | | | GD01602 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2320

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2323 | 286N2323 | | | EFIS DISP. UNITS-F/O (continued) | | | | | | | | | | | |
| 0015 | 20 | | GA | | 4-0 | 34-22-26 | D00097 | | 38 | | GD01602 | DC.. | 2 | | 001-099 |
| 0015 | 20 | | GA | | 7-0 | 34-22-26 | D00097 | | 38 | | GD01602 | DC.. | 2 | | 115-199 |
| 0016 | 24 | | GK | | 33-0 | 34-22-25 | D00093 | | 22 | | D41079P | | 28 | | ALL |
| 0017 | 24 | | GK | | 33-0 | 34-22-25 | D00093 | | 23 | | D41079P | | 29 | | ALL |
| 0018 | 24 | | GK | | 33-0 | 34-22-25 | D00093 | | 24 | | D41079P | | 30 | | ALL |
| 0019 | 24 | | GK | | 13-0 | 34-22-25 | D00093 | | 67 | | D00097 | | 23 | | 001-099 |
| 0019 | 24 | | GK | | 14-0 | 34-22-25 | D00093 | | 67 | | D00097 | | 23 | | 115-199 |
| 0020 | 24 | | GK | | 7-0 | 34-22-25 | D00093 | | 1 | | TB0016X | A005 | BJ | | 001-099 |
| 0020 | 24 | | GK | | 6-0 | 34-22-25 | D00093 | | 1 | | TB0016X | A005 | BJ | | 115-199 |
| 0021 | 24 | | GK | | 7-0 | 34-22-25 | D00093 | | 2 | | TB0016X | B005 | BJ | | 001-099 |
| 0021 | 24 | | GK | | 6-0 | 34-22-25 | D00093 | | 2 | | TB0016X | B005 | BJ | | 115-199 |
| 0022 | 24 | | GK | | 7-0 | 34-22-25 | D00093 | | 8 | | TB0016X | C005 | BJ | | 001-099 |
| 0022 | 24 | | GK | | 6-0 | 34-22-25 | D00093 | | 8 | | TB0016X | C005 | BJ | | 115-199 |
| 0023 | 24 | | GK | | 12-0 | 34-22-28 | D00097 | | 20 | | TB0016Y | A007 | BJ | | 001-099 |
| 0023 | 24 | | GK | | 13-0 | 34-22-28 | D00097 | | 20 | | TB0016Y | A007 | BJ | | 115-199 |
| 0024 | 24 | | GK | | 12-0 | 34-22-28 | D00097 | | 18 | | TB0016Y | A007 | BJ | | 001-099 |
| 0024 | 24 | | GK | | 13-0 | 34-22-28 | D00097 | | 18 | | TB0016Y | A007 | BJ | | 115-199 |
| 0025 | 24 | | GK | | 12-0 | 34-22-28 | D00097 | | 21 | | TB0016Z | | 11 | BJ | 001-099 |
| 0025 | 24 | | GK | | 13-0 | 34-22-28 | D00097 | | 21 | | TB0016Z | | 11 | BJ | 115-199 |
| 0026 | 24 | | GK | | 12-0 | 34-22-28 | D00097 | | 17 | | TB0016Z | | 11 | BJ | 001-099 |
| 0026 | 24 | | GK | | 13-0 | 34-22-28 | D00097 | | 17 | | TB0016Z | | 11 | BJ | 115-199 |
| 0027 | 22 | | GA | | 4-0 | 34-22-28 | D00097 | | 16 | | GD01602 | DC.. | 2 | | 001-099 |
| 0027 | 22 | | GA | | 7-0 | 34-22-28 | D00097 | | 16 | | GD01602 | DC.. | 2 | | 115-199 |
| 0028 | 24 | | GK | | 34-0 | 34-43-12 | D00097 | | 14 | | D41077P | | 34 | | 001, 003-099 |
| 0028 | 24 | | GK | | 34-0 | SPARE | D00097 | | 14 | | D41077P | | 34 | | 002 |
| 0028 | 24 | | GK | | 35-0 | 34-43-12 | D00097 | | 14 | | D41077P | | 42 | | 115-199 |
| 0030 | 24 | | GK | | 7-0 | 34-22-25 | D00093 | | 41 | | TB0015Y | A007 | BJ | | 001-099 |
| 0030 | 24 | | GK | | 6-0 | 34-22-25 | D00093 | | 41 | | TB0015Y | A007 | BJ | | 115-199 |
| 0031 | 20 | | GA | | 5-0 | 33-13-51 | D00097 | | 1 | | TB0100Y | A005 | BJ | | 001-099 |
| 0031 | 20 | | GA | | 7-0 | 33-13-51 | D00097 | | 1 | | TB0100Y | A005 | BJ | | 115-199 |
| 0032 | 20 | | GA | | 4-0 | 33-13-51 | D00097 | | 2 | | GD01604 | AC.. | 2 | | 001-099 |
| 0032 | 20 | | GA | | 7-0 | 33-13-51 | D00097 | | 2 | | GD01604 | AC.. | 2 | | 115-199 |
| 0035 | 24 | | GK | | 7-0 | 34-22-24 | D00091 | | 41 | | TB0015Y | A007 | BJ | | 001-099 |
| 0035 | 24 | | GK | | 6-0 | 34-22-24 | D00091 | | 41 | | TB0015Y | A007 | BJ | | 115-199 |
| 0037 | 20 | | GA | | 7-0 | 34-22-26 | D00097 | | 39 | | GD01602 | DC.. | 2 | | 115-199 |
| 2001B | 24 | | GL | AA | 4-0 | 34-22-24 | D00091 | | 13 | | D00093 | | 27 | | 001-099 |
| 2001B | 24 | | GL | AA | 3-0 | 34-22-24 | D00091 | | 13 | | D00093 | | 27 | | 115-199 |
| 2001R | 24 | | GL | AA | 0-0 | 34-22-24 | D00091 | | 12 | | D00093 | | 26 | | ALL |
| 2002B | 24 | | GL | AB | 4-0 | 34-22-24 | D00091 | | 27 | | D00093 | | 13 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2320

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2323 | 286N2323 | | | EFIS DISP. UNITS-F/O (continued) | | | | | | | | | | | |
| 2002B | 24 | GL | AB | 3-0 | 34-22-24 | D00091 | | 27 | | | D00093 | 13 | | | 115-199 |
| 2002R | 24 | GL | AB | 0-0 | 34-22-24 | D00091 | | 26 | | | D00093 | 12 | | | ALL |
| 2501T | 24 | BV | AE | 33-0 | 34-22-24 | D41077P | | 1 | | | D00091 | 49 | | | 001-099 |
| 2501T | 24 | BV | AE | 32-0 | 34-22-24 | D41077P | | 1 | | | D00091 | 49 | | | 115-199 |
| 2501W | 24 | BV | AE | 0-0 | 34-22-24 | D41077P | | 2 | | | D00091 | 50 | | | ALL |
| 2501Z | | | AE | 0-0 | 34-22-24 | D41077P | | 3 | | | GD02445 | ST.. | 2 | | ALL |
| 2502T | 24 | BV | AF | 33-0 | 34-22-24 | D41077P | | 4 | | | D00091 | 51 | | | 001-099 |
| 2502T | 24 | BV | AF | 32-0 | 34-22-24 | D41077P | | 4 | | | D00091 | 51 | | | 115-199 |
| 2502W | 24 | BV | AF | 0-0 | 34-22-24 | D41077P | | 5 | | | D00091 | 52 | | | ALL |
| 2502Z | | | AF | 0-0 | 34-22-24 | D41077P | | 6 | | | GD02445 | ST.. | 2 | | ALL |
| 2503T | 24 | BV | AG | 33-0 | 34-22-24 | D41077P | | 7 | | | D00091 | 53 | | | 001-099 |
| 2503T | 24 | BV | AG | 32-0 | 34-22-24 | D41077P | | 7 | | | D00091 | 53 | | | 115-199 |
| 2503W | 24 | BV | AG | 0-0 | 34-22-24 | D41077P | | 8 | | | D00091 | 54 | | | ALL |
| 2503Z | | | AG | 0-0 | 34-22-24 | D41077P | | 9 | | | GD02445 | ST.. | 2 | | ALL |
| 2504T | 24 | BV | AH | 33-0 | 34-22-24 | D41077P | | 10 | | | D00091 | 55 | | | ALL |
| 2504W | 24 | BV | AH | 0-0 | 34-22-24 | D41077P | | 11 | | | D00091 | 56 | | | ALL |
| 2504Z | | | AH | 0-0 | 34-22-24 | D41077P | | 12 | | | GD01847 | ST.. | 2 | | ALL |
| 2505T | 24 | BV | AI | 33-0 | 34-22-24 | D41077P | | 13 | | | D00091 | 57 | | | ALL |
| 2505W | 24 | BV | AI | 0-0 | 34-22-24 | D41077P | | 14 | | | D00091 | 58 | | | ALL |
| 2505Z | | | AI | 0-0 | 34-22-24 | D41077P | | 15 | | | GD01847 | ST.. | 2 | | ALL |
| 2506T | 24 | BV | AJ | 33-0 | 34-22-24 | D41077P | | 16 | | | D00091 | 59 | | | ALL |
| 2506W | 24 | BV | AJ | 0-0 | 34-22-24 | D41077P | | 17 | | | D00091 | 60 | | | ALL |
| 2506Z | | | AJ | 0-0 | 34-22-24 | D41077P | | 18 | | | GD01847 | ST.. | 2 | | ALL |
| 2507T | 24 | BV | AK | 33-0 | 34-22-24 | D41077P | | 19 | | | D00091 | 61 | | | ALL |
| 2507W | 24 | BV | AK | 0-0 | 34-22-24 | D41077P | | 20 | | | D00091 | 62 | | | ALL |
| 2507Z | | | AK | 0-0 | 34-22-24 | D41077P | | 21 | | | GD01847 | ST.. | 2 | | ALL |
| 2508T | 24 | BV | AL | 33-0 | 34-22-24 | D41077P | | 22 | | | D00091 | 63 | | | ALL |
| 2508W | 24 | BV | AL | 0-0 | 34-22-24 | D41077P | | 23 | | | D00091 | 64 | | | ALL |
| 2508Z | | | AL | 0-0 | 34-22-24 | D41077P | | 24 | | | GD01847 | ST.. | 2 | | ALL |
| 2509T | 24 | BV | AM | 33-0 | 34-22-24 | D41077P | | 25 | | | D00091 | 65 | | | 001-099 |
| 2509T | 24 | BV | AM | 35-0 | 34-22-24 | D41077P | | 25 | | | D00091 | 65 | | | 115-199 |
| 2509W | 24 | BV | AM | 0-0 | 34-22-24 | D41077P | | 26 | | | D00091 | 66 | | | ALL |
| 2509Z | | | AM | 0-0 | 34-22-24 | D41077P | | 27 | | | GD01847 | ST.. | 2 | | ALL |
| 2510B | 24 | G2 | AC | 6-0 | 34-22-24 | D00091 | | 29 | | | TB0016Z | 30 | BJ | | ALL |
| 2510R | 24 | G2 | AC | 0-0 | 34-22-24 | D00091 | | 28 | | | TB0016Z | 29 | BJ | | ALL |
| 2510Z | | | AC | 0-0 | 34-22-24 | GD01847 | | ST.. | 2 | | TB0016Z | 31 | BJ | | ALL |
| 2511T | 24 | BV | AN | 33-0 | 34-22-25 | D41079P | | 1 | | | D00093 | 49 | | | ALL |
| 2511W | 24 | BV | AN | 0-0 | 34-22-25 | D41079P | | 2 | | | D00093 | 50 | | | ALL |
| 2511Z | | | AN | 0-0 | 34-22-25 | D41079P | | 3 | | | GD01719 | ST.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2320

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|----------------------------------|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2323 | 286N2323 | | | EFIS DISP. UNITS-F/O (continued) | | | | | | | | | | | | |
| 2512T | 24 | BV | AO | | 33-0 | 34-22-25 | D41079P | | 4 | | | D00093 | 51 | | | ALL |
| 2512W | 24 | BV | AO | | 0-0 | 34-22-25 | D41079P | | 5 | | | D00093 | 52 | | | ALL |
| 2512Z | | | AO | | 0-0 | 34-22-25 | D41079P | | 6 | | | GD01719 | ST.. | 2 | | ALL |
| 2513T | 24 | BV | AP | | 33-0 | 34-22-25 | D41079P | | 7 | | | D00093 | 53 | | | ALL |
| 2513W | 24 | BV | AP | | 0-0 | 34-22-25 | D41079P | | 8 | | | D00093 | 54 | | | ALL |
| 2513Z | | | AP | | 0-0 | 34-22-25 | D41079P | | 9 | | | GD01719 | ST.. | 2 | | ALL |
| 2514T | 24 | BV | AQ | | 33-0 | 34-22-25 | D41079P | | 10 | | | D00093 | 55 | | | ALL |
| 2514W | 24 | BV | AQ | | 0-0 | 34-22-25 | D41079P | | 11 | | | D00093 | 56 | | | ALL |
| 2514Z | | | AQ | | 0-0 | 34-22-25 | D41079P | | 12 | | | GD01719 | ST.. | 2 | | ALL |
| 2515T | 24 | BV | AR | | 33-0 | 34-22-25 | D41079P | | 13 | | | D00093 | 57 | | | ALL |
| 2515W | 24 | BV | AR | | 0-0 | 34-22-25 | D41079P | | 14 | | | D00093 | 58 | | | ALL |
| 2515Z | | | AR | | 0-0 | 34-22-25 | D41079P | | 15 | | | GD01719 | ST.. | 2 | | ALL |
| 2516T | 24 | BV | AS | | 33-0 | 34-22-25 | D41079P | | 16 | | | D00093 | 59 | | | ALL |
| 2516W | 24 | BV | AS | | 0-0 | 34-22-25 | D41079P | | 17 | | | D00093 | 60 | | | ALL |
| 2516Z | | | AS | | 0-0 | 34-22-25 | D41079P | | 18 | | | GD02447 | ST.. | 2 | | ALL |
| 2517T | 24 | BV | AT | | 33-0 | 34-22-25 | D41079P | | 19 | | | D00093 | 61 | | | ALL |
| 2517W | 24 | BV | AT | | 0-0 | 34-22-25 | D41079P | | 20 | | | D00093 | 62 | | | ALL |
| 2517Z | | | AT | | 0-0 | 34-22-25 | D41079P | | 21 | | | GD02447 | ST.. | 2 | | ALL |
| 2518T | 24 | BV | AU | | 33-0 | 34-22-25 | D41079P | | 22 | | | D00093 | 63 | | | ALL |
| 2518W | 24 | BV | AU | | 0-0 | 34-22-25 | D41079P | | 23 | | | D00093 | 64 | | | ALL |
| 2518Z | | | AU | | 0-0 | 34-22-25 | D41079P | | 24 | | | GD02447 | ST.. | 2 | | ALL |
| 2519T | 24 | BV | AV | | 33-0 | 34-22-25 | D41079P | | 25 | | | D00093 | 65 | | | ALL |
| 2519W | 24 | BV | AV | | 0-0 | 34-22-25 | D41079P | | 26 | | | D00093 | 66 | | | ALL |
| 2519Z | | | AV | | 0-0 | 34-22-25 | D41079P | | 27 | | | GD01719 | ST.. | 2 | | ALL |
| 2520B | 24 | G2 | AD | | 6-0 | 34-22-25 | D00093 | | 29 | | | TB0016Z | 30 | BJ | | ALL |
| 2520R | 24 | G2 | AD | | 0-0 | 34-22-25 | D00093 | | 28 | | | TB0016Z | 29 | BJ | | ALL |
| 2520Z | | | AD | | 0-0 | 34-22-25 | GD01719 | ST.. | 2 | | | TB0016Z | 31 | BJ | | ALL |
| 3001B | 24 | GM | AX | | 13-0 | 34-22-24 | D00091 | | 31 | | | D00097 | 32 | | | 001-099 |
| 3001B | 24 | GM | AX | | 14-0 | 34-22-24 | D00091 | | 31 | | | D00097 | 32 | | | 115-199 |
| 3001R | 24 | GM | AX | | 0-0 | 34-22-24 | D00091 | | 30 | | | D00097 | 33 | | | ALL |
| 3001Y | 24 | GM | AX | | 0-0 | 34-22-24 | D00091 | | 32 | | | D00097 | 31 | | | ALL |
| 3002B | 24 | GM | AY | | 13-0 | 34-22-25 | D00093 | | 34 | | | D00097 | 29 | | | 001-099 |
| 3002B | 24 | GM | AY | | 14-0 | 34-22-25 | D00093 | | 34 | | | D00097 | 29 | | | 115-199 |
| 3002R | 24 | GM | AY | | 0-0 | 34-22-25 | D00093 | | 33 | | | D00097 | 30 | | | ALL |
| 3002Y | 24 | GM | AY | | 0-0 | 34-22-25 | D00093 | | 35 | | | D00097 | 28 | | | ALL |
| 3003B | 24 | GM | AZ | | 13-0 | 34-22-25 | D00093 | | 31 | | | D00097 | 26 | | | 001-099 |
| 3003B | 24 | GM | AZ | | 14-0 | 34-22-25 | D00093 | | 31 | | | D00097 | 26 | | | 115-199 |
| 3003R | 24 | GM | AZ | | 0-0 | 34-22-25 | D00093 | | 30 | | | D00097 | 27 | | | ALL |
| 3003Y | 24 | GM | AZ | | 0-0 | 34-22-25 | D00093 | | 32 | | | D00097 | 25 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2320

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|----------------------------------|---------|----------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2323 | 286N2323 | | | EFIS DISP. UNITS-F/O (continued) | | | | | | | | | | | |
| 5001B | 24 | | G2 | BA | 34-0 | 34-22-24 | D00097 | 35 | | | D41077P | 31 | | | 001-099 |
| 5001B | 24 | | G2 | BA | 35-0 | 34-22-24 | D00097 | 35 | | | D41077P | 31 | | | 115-199 |
| 5001R | 24 | | G2 | BA | 0-0 | 34-22-24 | D00097 | 36 | | | D41077P | 32 | | | ALL |
| 5001Z | | | | BA | 0-0 | 34-22-24 | GD01645 | ST.. | E | | D41077P | 33 | | | ALL |
| W2329 | 286N2329 | | | FMCS DATA LOAD TO E/E BAY | | | | | | | | | | | |
| 0162 | 24 | | GK | | 29-0 | 34-61-14 | D42183P | 11 | | | D00917 | 11 | | | 001-099 |
| 0162 | 24 | | GK | | 27-0 | 34-61-14 | D42183P | 11 | | | D00917 | 11 | | | 115-199 |
| 0167 | 22 | | GA | | 29-0 | 34-61-15 | D42183P | 13 | | | D00917 | 13 | | | 001-099 |
| 0167 | 22 | | GA | | 27-0 | 34-61-15 | D42183P | 13 | | | D00917 | 13 | | | 115-199 |
| 0168 | 20 | | GA | | 29-0 | 34-61-15 | D42183P | 14 | | | D00917 | 14 | | | 001-099 |
| 0168 | 20 | | GA | | 27-0 | 34-61-15 | D42183P | 14 | | | D00917 | 14 | | | 115-199 |
| 0169 | 20 | | GA | | 29-0 | 34-61-15 | D42183P | 15 | | | D00917 | 15 | | | 001-099 |
| 0169 | 20 | | GA | | 27-0 | 34-61-15 | D42183P | 15 | | | D00917 | 15 | | | 115-199 |
| 0354 | 20 | | GA | | 29-0 | 34-61-14 | D42183P | 12 | | | D00917 | 12 | | | 001-099 |
| 0354 | 20 | | GA | | 27-0 | 34-61-14 | D42183P | 12 | | | D00917 | 12 | | | 115-199 |
| 5080B | 24 | | G2 | AA | 29-0 | 34-61-14 | D42183P | 1 | | | D00917 | 1 | | | 001-099 |
| 5080B | 24 | | G2 | AA | 27-0 | 34-61-14 | D42183P | 1 | | | D00917 | 1 | | | 115-199 |
| 5080R | 24 | | G2 | AA | 0-0 | 34-61-14 | D42183P | 2 | | | D00917 | 2 | | | ALL |
| 5080Z | | | | AA | 0-0 | 34-61-14 | D42183P | 5 | | | D00917 | DED | | | ALL |
| 5081B | 24 | | G2 | AB | 29-0 | 34-61-15 | D42183P | 4 | | | D00917 | 4 | | | 001-099 |
| 5081B | 24 | | G2 | AB | 27-0 | 34-61-15 | D42183P | 4 | | | D00917 | 4 | | | 115-199 |
| 5081R | 24 | | G2 | AB | 0-0 | 34-61-15 | D42183P | 3 | | | D00917 | 3 | | | ALL |
| 5081Z | | | | AB | 0-0 | 34-61-15 | D42183P | 8 | | | D00917 | DED | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2320

Page 8 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2331 | 286N2331 | | | | LEFT FMC/CDU INTERFACE | | | | | | | | | | | | |
| 0001 | 24 | | GK | | 5-0 | 34-61-11 | D00171 | | 30 | | | TB0101X | D002 | BJ | | 001-099 | |
| 0001 | 24 | | GK | | 8-0 | 34-61-11 | D00171 | | 40 | | | TB0101X | D002 | BJ | | 115-199 | |
| 0002 | 20 | | GA | | 6-0 | 34-61-11 | D00171 | | 31 | | | GD00108 | AC.. | 2 | | 001-099 | |
| 0002 | 20 | | GA | | 7-0 | 34-61-11 | D00171 | | 41 | | | GD00108 | AC.. | 2 | | 115-199 | |
| 0003 | 20 | | GA | | 6-0 | 34-61-11 | D00171 | | 25 | | | GD00108 | DC.. | 2 | | 001-099 | |
| 0003 | 20 | | GA | | 7-0 | 34-61-11 | D00171 | | 34 | | | GD00108 | DC.. | 2 | | 115-199 | |
| 0004 | 24 | | GK | | 33-0 | 34-61-11 | D00171 | | 13 | | | D41081P | 10 | | | 001-099 | |
| 0004 | 24 | | GK | | 32-0 | 34-61-11 | D00171 | | CAP | Y | | D41081P | 10 | | | 115-199 | |
| 0005 | 20 | | GA | | 6-0 | 34-61-11 | D00171 | | 26 | | | GD00108 | DC.. | 2 | | 001-099 | |
| 0005 | 20 | | GA | | 7-0 | 34-61-11 | D00171 | | 36 | | | GD00108 | DC.. | 2 | | 115-199 | |
| 0006 | 22 | | GA | | 14-0 | 33-16-51 | D00171 | | 27 | | | TB0100Y | C005 | BJ | | 001-099 | |
| 0006 | 22 | | GA | | 14-0 | 33-16-51 | D00171 | | 35 | | | TB0100Y | C005 | BJ | | 115-199 | |
| 0007 | 22 | | GA | | 14-0 | 33-16-51 | D00171 | | 23 | | | TB0100Y | A009 | BJ | | 001-099 | |
| 0007 | 22 | | GA | | 14-0 | 33-16-51 | D00171 | | 33 | | | TB0100Y | A009 | BJ | | 115-199 | |
| 0008 | 20 | | GA | | 5-0 | 33-13-52 | D00171 | | 28 | | | TB0101Y | A003 | BJ | | 001-099 | |
| 0008 | 20 | | GA | | 8-0 | 33-13-52 | D00171 | | 37 | | | TB0101Y | A003 | BJ | | 115-199 | |
| 0009 | 20 | | GA | | 6-0 | 33-13-52 | D00171 | | 29 | | | GD00108 | AC.. | 2 | | 001-099 | |
| 0009 | 20 | | GA | | 7-0 | 33-13-52 | D00171 | | 38 | | | GD00108 | AC.. | 2 | | 115-199 | |
| 0010 | 24 | | GK | | 13-0 | 34-61-11 | D00171 | | 10 | | | TB0014Y | C009 | BJ | | 001-099 | |
| 0011 | 22 | | GA | | 6-0 | 34-61-11 | D00171 | | 11 | | | GD00108 | DC.. | 2 | | 001-099 | |
| 0011 | 22 | | GA | | 7-0 | 34-61-11 | D00171 | | 30 | | | GD00108 | DC.. | 2 | | 115-199 | |
| 0012 | 22 | | PA | | 13-0 | 34-61-16 | D01487 | | 23 | | | TB0013Y | A017 | BJ | | 115-199 | |
| 0015 | 22 | | PA | | 13-0 | 34-61-16 | D01487 | | 18 | | | GD00108 | DC.. | 2 | | 115-199 | |
| 0016 | 22 | | PA | | 13-0 | 34-61-16 | D00171 | | 21 | | | TB0013Y | A018 | BJ | | 115-199 | |
| 5001B | 24 | | G2 | AA | 33-0 | 34-61-11 | D00171 | | 3 | | | D41081P | 7 | | | 001-099 | |
| 5001B | 24 | | G2 | AA | 32-0 | 34-61-11 | D00171 | | 3 | | | D41081P | 7 | | | 115-199 | |
| 5001R | 24 | | G2 | AA | 0-0 | 34-61-11 | D00171 | | 2 | | | D41081P | 8 | | | ALL | |
| 5001Z | | | | AA | 0-0 | 34-61-11 | GD01100 | | ST.. | E | | D41081P | 9 | | | ALL | |
| 5002B | 24 | | G2 | AB | 33-0 | 34-61-11 | D00171 | | 9 | | | D41081P | 4 | | | 001-099 | |
| 5002B | 24 | | G2 | AB | 32-0 | 34-61-11 | D00171 | | 25 | | | D41081P | 4 | | | 115-199 | |
| 5002R | 24 | | G2 | AB | 0-0 | 34-61-11 | D00171 | | 8 | | | D41081P | 5 | | | 001-099 | |
| 5002R | 24 | | G2 | AB | 0-0 | 34-61-11 | D00171 | | 26 | | | D41081P | 5 | | | 115-199 | |
| 5002Z | | | | AB | 0-0 | 34-61-11 | GD01100 | | ST.. | E | | D41081P | 6 | | | ALL | |
| 5003B | 24 | | G2 | AC | 33-0 | 34-61-11 | D00171 | | 6 | | | D41081P | 1 | | | 001-099 | |
| 5003B | 24 | | G2 | AC | 32-0 | 34-61-11 | D00171 | | 6 | | | D41081P | 1 | | | 115-199 | |
| 5003R | 24 | | G2 | AC | 0-0 | 34-61-11 | D00171 | | 5 | | | D41081P | 2 | | | ALL | |
| 5003Z | | | | AC | 0-0 | 34-61-11 | GD01100 | | ST.. | E | | D41081P | 3 | | | ALL | |
| 5004B | 24 | | G2 | AD | 32-0 | SPARE | D00171 | | CAP | Y | | D41081P | 13 | | | 115-199 | |
| 5004R | 24 | | G2 | AD | 0-0 | SPARE | D00171 | | CAP | Y | | D41081P | 12 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W2330

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|--|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2331 | | 286N2331 | | | LEFT FMC/CDU INTERFACE (continued) | | | | | | | | | | | |
| 5004Z | | | | | AD | 0-0 | SPARE | GD01100 | ST.. | E | | D41081P | 14 | | | 115-199 |
| 5005B | | 22 | | X2 | AI | 33-0 | 34-61-11 | D01487 | 3 | | | D41081P | 22 | | | 115-199 |
| 5005R | | 22 | | X2 | AI | 0-0 | 34-61-11 | D01487 | 2 | | | D41081P | 23 | | | 115-199 |
| 5005Z | | | | | AI | 0-0 | 34-61-11 | GD01100 | ST.. | E | | D41081P | 18 | | | 115-199 |
| 5006B | | 24 | | G2 | AD | 33-0 | 34-61-11 | D41081P | 20 | | | D00171 | 17 | VP | | 001-099 |
| 5006B | | 22 | | X2 | AH | 33-0 | 34-61-11 | D01487 | 6 | | | D41081P | 20 | | | 115-199 |
| 5006R | | 24 | | G2 | AD | 0-0 | 34-61-11 | D41081P | 19 | | | D00171 | 16 | VP | | 001-099 |
| 5006R | | 22 | | X2 | AH | 0-0 | 34-61-11 | D01487 | 5 | | | D41081P | 19 | | | 115-199 |
| 5006Z | | | | | AD | 0-0 | 34-61-11 | D41081P | 21 | | | GD01100 | ST.. | E | | 001-099 |
| 5006Z | | | | | AH | 0-0 | 34-61-11 | GD01100 | ST.. | E | | D41081P | 21 | | | 115-199 |
| 5007B | | 22 | | X2 | AJ | 33-0 | 34-61-16 | D01487 | 9 | | | D41081P | 16 | | | 115-199 |
| 5007R | | 22 | | X2 | AJ | 0-0 | 34-61-16 | D01487 | 8 | | | D41081P | 17 | | | 115-199 |
| 5007Z | | | | | AJ | 0-0 | 34-61-16 | GD01100 | ST.. | E | | D41081P | 15 | | | 115-199 |
| W2333 | | 286N2333 | | | RIGHT FMC/CDU INTERFACE | | | | | | | | | | | |
| 0001 | | 24 | | GK | | 7-0 | 34-61-21 | D00175 | 30 | | | TB0100X | D004 | BJ | | 001-099 |
| 0001 | | 24 | | GK | | 6-0 | 34-61-21 | D00175 | 40 | | | TB0100X | D004 | BJ | | 115-199 |
| 0002 | | 20 | | GA | | 10-0 | 34-61-21 | D00175 | 31 | | | GD00109 | AC.. | 2 | | 001-099 |
| 0002 | | 20 | | GA | | 8-0 | 34-61-21 | D00175 | 41 | | | GD00109 | AC.. | 2 | | 115-199 |
| 0003 | | 20 | | GA | | 10-0 | 34-61-21 | D00175 | 26 | | | GD00109 | DC.. | 2 | | 001-099 |
| 0003 | | 20 | | GA | | 8-0 | 34-61-21 | D00175 | 36 | | | GD00109 | DC.. | 2 | | 115-199 |
| 0004 | | 20 | | GA | | 10-0 | 34-61-21 | D00175 | 25 | | | GD00109 | ST.. | 2 | | 001-099 |
| 0004 | | 20 | | GA | | 7-0 | 34-61-21 | D00175 | 34 | | | GD00109 | ST.. | 2 | | 115-199 |
| 0005 | | 24 | | GK | | 35-0 | 34-61-21 | D00175 | 13 | | | D41083P | 11 | | | 001-099 |
| 0005 | | 24 | | GK | | 34-0 | 34-61-21 | D00175 | CAP | Y | | D41083P | 11 | | | 115-199 |
| 0006 | | 22 | | GA | | 7-0 | 33-16-41 | D00175 | 23 | | | TB0100X | C003 | BJ | | 001-099 |
| 0006 | | 22 | | GA | | 6-0 | 33-16-41 | D00175 | 33 | | | TB0100X | C003 | BJ | | 115-199 |
| 0007 | | 22 | | GA | | 7-0 | 33-16-31 | D00175 | 27 | | | TB0100X | A003 | BJ | | 001-099 |
| 0007 | | 22 | | GA | | 6-0 | 33-16-31 | D00175 | 35 | | | TB0100X | A003 | BJ | | 115-199 |
| 0008 | | 20 | | GA | | 7-0 | 33-13-51 | D00175 | 28 | | | TB0100Y | A005 | BJ | | 001-099 |
| 0008 | | 20 | | GA | | 6-0 | 33-13-51 | D00175 | 37 | | | TB0100Y | A005 | BJ | | 115-199 |
| 0009 | | 20 | | GA | | 10-0 | 33-13-51 | D00175 | 29 | | | GD00109 | AC.. | 2 | | 001-099 |
| 0009 | | 20 | | GA | | 8-0 | 33-13-51 | D00175 | 38 | | | GD00109 | AC.. | 2 | | 115-199 |
| 0010 | | 24 | | GK | | 22-0 | 34-61-21 | D00175 | 10 | | | TB0015X | B021 | BJ | | 001-099 |
| 0010 | | 24 | | GK | | 20-0 | 34-61-26 | D00175 | 29 | | | TB0015X | B021 | BJ | | 115-199 |
| 0011 | | 22 | | GA | | 10-0 | 34-61-21 | D00175 | 12 | | | GD00109 | DC.. | 2 | | 001-099 |
| 0011 | | 22 | | GA | | 8-0 | 34-61-21 | D00175 | 31 | | | GD00109 | DC.. | 2 | | 115-199 |
| 0012 | | 22 | | PA | | 20-0 | 34-61-26 | D01489 | 23 | | | TB0015X | A021 | BJ | | 115-199 |
| 0015 | | 22 | | PA | | 11-0 | 34-61-26 | D01489 | 18 | | | GD00109 | DC.. | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2330

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2333 | 286N2333 | | | RIGHT FMC/CDU INTERFACE (continued) | | | | | | | | | | | | |
| 5001B | 24 | G2 | AA | | 35-0 | 34-61-21 | D00175 | | 3 | | | D41083P | | 3 | | 001-099 |
| 5001B | 24 | G2 | AA | | 34-0 | 34-61-21 | D00175 | | 3 | | | D41083P | | 3 | | 115-199 |
| 5001R | 24 | G2 | AA | | 0-0 | 34-61-21 | D00175 | | 2 | | | D41083P | | 2 | | ALL |
| 5001Z | | | AA | | 0-0 | 34-61-21 | GD01200 | ST.. | E | | | D41083P | | 4 | | ALL |
| 5002B | 24 | G2 | AB | | 35-0 | 34-61-21 | D00175 | | 9 | | | D41083P | | 6 | | 001-099 |
| 5002B | 24 | G2 | AB | | 34-0 | 34-61-21 | D00175 | | 28 | | | D41083P | | 6 | | 115-199 |
| 5002R | 24 | G2 | AB | | 0-0 | 34-61-21 | D00175 | | 8 | | | D41083P | | 5 | | 001-099 |
| 5002R | 24 | G2 | AB | | 0-0 | 34-61-21 | D00175 | | 27 | | | D41083P | | 5 | | 115-199 |
| 5002Z | | | AB | | 0-0 | 34-61-21 | GD01200 | ST.. | E | | | D41083P | | 7 | | ALL |
| 5003B | 24 | G2 | AC | | 35-0 | 34-61-21 | D00175 | | 6 | | | D41083P | | 9 | | 001-099 |
| 5003B | 24 | G2 | AC | | 34-0 | 34-61-21 | D00175 | | 6 | | | D41083P | | 9 | | 115-199 |
| 5003R | 24 | G2 | AC | | 0-0 | 34-61-21 | D00175 | | 5 | | | D41083P | | 8 | | ALL |
| 5003Z | | | AC | | 0-0 | 34-61-21 | GD01200 | ST.. | E | | | D41083P | | 10 | | ALL |
| 5004B | 24 | G2 | AD | | 34-0 | SPARE | D00175 | CAP | Y | | | D41083P | | 13 | | 115-199 |
| 5004R | 24 | G2 | AD | | 0-0 | SPARE | D00175 | CAP | Y | | | D41083P | | 12 | | 115-199 |
| 5004Z | | | AD | | 0-0 | SPARE | D00175 | DED | | | | D41083P | | 14 | | 115-199 |
| 5005B | 22 | X2 | AE | | 41-0 | 34-61-21 | D01489 | | 3 | | | D41083P | | 17 | | 115-199 |
| 5005R | 22 | X2 | AE | | 0-0 | 34-61-21 | D01489 | | 2 | | | D41083P | | 16 | | 115-199 |
| 5005Z | | | AE | | 0-0 | 34-61-21 | D41083P | | 18 | | | GD01200 | ST.. | E | | 115-199 |
| 5006B | 24 | G2 | AD | | 34-0 | 34-61-21 | D00175 | | 17 | VP | | D41083P | | 20 | | 001-099 |
| 5006B | 22 | X2 | AF | | 41-0 | 34-61-21 | D01489 | | 6 | | | D41083P | | 20 | | 115-199 |
| 5006R | 24 | G2 | AD | | 0-0 | 34-61-21 | D00175 | | 16 | VP | | D41083P | | 19 | | 001-099 |
| 5006R | 22 | X2 | AF | | 0-0 | 34-61-21 | D01489 | | 5 | | | D41083P | | 19 | | 115-199 |
| 5006Z | | | AD | | 0-0 | 34-61-21 | GD01200 | ST.. | E | | | D41083P | | 21 | | 001-099 |
| 5006Z | | | AF | | 0-0 | 34-61-21 | GD01200 | ST.. | E | | | D41083P | | 21 | | 115-199 |
| 5007B | 22 | X2 | AG | | 41-0 | 34-61-26 | D01489 | | 9 | | | D41083P | | 22 | | 115-199 |
| 5007R | 22 | X2 | AG | | 0-0 | 34-61-26 | D01489 | | 8 | | | D41083P | | 23 | | 115-199 |
| 5007Z | | | AG | | 0-0 | 34-61-26 | GD01200 | ST.. | E | | | D41083P | | 24 | | 115-199 |
| W2335 | 286N2335 | | | FLIGHT INTERPHONE-CAPT, P08 TO E/E SHELF | | | | | | | | | | | | |
| 4501 | 20 | VA | AA | | 43-0 | 23-51-14 | D41553P | | 20 | | | D00337 | | 20 | | ALL |
| 4501AA | 24 | VA | AA | | 0-0 | 23-51-11 | D41553P | | 19 | | | D00337 | | 19 | | ALL |
| 4501AB | 24 | VA | AA | | 0-0 | 23-51-12 | D41553P | | 27 | | | D00337 | | 27 | | ALL |
| 4501AC | 24 | VA | AA | | 0-0 | 23-51-13 | D41553P | | 34 | | | D00337 | | 34 | | ALL |
| 4501AD | 20 | VA | AA | | 0-0 | 23-51-11 | D41553P | | 1 | | | D00337 | | 1 | | ALL |
| 4501B | 24 | VA | AA | | 0-0 | 23-51-11 | D41553P | | 2 | | | D00337 | | 2 | | ALL |
| 4501BG | 24 | VA | AA | | 0-0 | 23-51-12 | D41553P | | 29 | | | D00337 | | 29 | | ALL |
| 4501BK | 24 | VA | AA | | 0-0 | 23-51-12 | D41553P | | 30 | | | D00337 | | 30 | | ALL |
| 4501BL | 24 | VA | AA | | 0-0 | 23-51-12 | D41553P | | 31 | | | D00337 | | 31 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2330

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|----------|---------|-------|------|------|--------|--------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2335 | 286N2335 | | | FLIGHT INTERPHONE-CAPT, P08 TO E/E SHELF (continued) | | | | | | | | | | | |
| 4501BN | 24 | VA | AA | 0-0 | 23-51-13 | D41553P | | 33 | | | D00337 | 33 | | | ALL |
| 4501BO | 24 | VA | AA | 0-0 | 23-51-13 | D41553P | | 32 | | | D00337 | 32 | | | ALL |
| 4501BY | 24 | VA | AA | 0-0 | 23-51-13 | D41553P | | 28 | | | D00337 | 28 | | | ALL |
| 4501G | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 4 | | | D00337 | 4 | | | ALL |
| 4501K | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 5 | | | D00337 | 5 | | | ALL |
| 4501L | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 6 | | | D00337 | 6 | | | ALL |
| 4501N | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 8 | | | D00337 | 8 | | | ALL |
| 4501O | 24 | VA | AA | 0-0 | 23-51-13 | D41553P | | 7 | | | D00337 | 7 | | | ALL |
| 4501P | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 9 | | | D00337 | 9 | | | ALL |
| 4501RG | 24 | VA | AA | 0-0 | 23-51-14 | D41553P | | 22 | | | D00337 | 22 | | | ALL |
| 4501RK | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 23 | | | D00337 | 23 | | | ALL |
| 4501RL | 24 | VA | AA | 0-0 | 23-51-14 | D41553P | | 24 | | | D00337 | 24 | | | ALL |
| 4501RN | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 26 | | | D00337 | 26 | | | ALL |
| 4501RO | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 25 | | | D00337 | 25 | | | ALL |
| 4501RY | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 21 | | | D00337 | 21 | | | ALL |
| 4501W | 24 | VA | AA | 0-0 | 23-51-14 | D41553P | | 10 | | | D00337 | 10 | | | ALL |
| 4501WB | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 12 | | | D00337 | 12 | | | ALL |
| 4501WG | 24 | VA | AA | 0-0 | 23-51-14 | D41553P | | 14 | | | D00337 | 14 | | | ALL |
| 4501WK | 24 | VA | AA | 0-0 | 23-51-14 | D41553P | | 15 | | | D00337 | 15 | | | ALL |
| 4501WL | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 16 | | | D00337 | 16 | | | ALL |
| 4501WN | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 18 | | | D00337 | 18 | | | ALL |
| 4501WO | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 17 | | | D00337 | 17 | | | ALL |
| 4501WR | 24 | VA | AA | 0-0 | 23-51-14 | D41553P | | 11 | | | D00337 | 11 | | | ALL |
| 4501WY | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 13 | | | D00337 | 13 | | | ALL |
| 4501Y | 24 | VA | AA | 0-0 | 23-51-11 | D41553P | | 3 | | | D00337 | 3 | | | ALL |
| 4501YG | 24 | VA | AA | 0-0 | 23-51-12 | D41553P | | 35 | | | D00337 | 35 | | | ALL |
| 4501YK | 24 | VA | AA | 0-0 | 23-51-12 | D41553P | | 36 | | | D00337 | 36 | | | ALL |
| 4501YL | 24 | VA | AA | 0-0 | 23-51-12 | D41553P | | 37 | | | D00337 | 37 | | | ALL |
| 4501YO | 24 | VA | AA | 0-0 | 23-51-13 | D41553P | | 38 | | | D00337 | 38 | | | ALL |
| W2337 | 286N2337 | | | FLIGHT-INTERPHONE-F/O, P08 TO E/E SHELF | | | | | | | | | | | |
| 4501 | 20 | VA | AA | 43-0 | 23-51-21 | D41555P | | 20 | | | D00449 | 20 | | | ALL |
| 4501AA | 24 | VA | AA | 0-0 | 23-51-21 | D41555P | | 19 | | | D00449 | 19 | | | ALL |
| 4501AB | 24 | VA | AA | 0-0 | 23-51-21 | D41555P | | 27 | | | D00449 | 27 | | | ALL |
| 4501AC | 24 | VA | AA | 0-0 | 23-51-21 | D41555P | | 34 | | | D00449 | 34 | | | ALL |
| 4501AD | 20 | VA | AA | 0-0 | 23-51-21 | D41555P | | 1 | | | D00449 | 1 | | | ALL |
| 4501B | 24 | VA | AA | 0-0 | 23-51-21 | D41555P | | 2 | | | D00449 | 2 | | | ALL |
| 4501BG | 24 | VA | AA | 0-0 | 23-51-21 | D41555P | | 29 | | | D00449 | 29 | | | ALL |
| 4501BK | 24 | VA | AA | 0-0 | 23-51-21 | D41555P | | 30 | | | D00449 | 30 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2330

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2337 | 286N2337 | | | FLIGHT-INTERPHONE-F/O, P08 TO E/E SHELF (continued) | | | | | | | | | | | |
| 4501BL | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 31 | | D00449 | | 31 | | ALL |
| 4501BN | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 33 | | D00449 | | 33 | | ALL |
| 4501BO | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 32 | | D00449 | | 32 | | ALL |
| 4501BY | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 28 | | D00449 | | 28 | | ALL |
| 4501G | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 4 | | D00449 | | 4 | | ALL |
| 4501K | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 5 | | D00449 | | 5 | | ALL |
| 4501L | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 6 | | D00449 | | 6 | | ALL |
| 4501N | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 8 | | D00449 | | 8 | | ALL |
| 4501O | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 7 | | D00449 | | 7 | | ALL |
| 4501P | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 9 | | D00449 | | 9 | | ALL |
| 4501RG | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 22 | | D00449 | | 22 | | ALL |
| 4501RK | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 23 | | D00449 | | 23 | | ALL |
| 4501RL | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 24 | | D00449 | | 24 | | ALL |
| 4501RN | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 26 | | D00449 | | 26 | | ALL |
| 4501RO | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 25 | | D00449 | | 25 | | ALL |
| 4501RY | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 21 | | D00449 | | 21 | | ALL |
| 4501W | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 10 | | D00449 | | 10 | | ALL |
| 4501WB | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 12 | | D00449 | | 12 | | ALL |
| 4501WG | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 14 | | D00449 | | 14 | | ALL |
| 4501WK | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 15 | | D00449 | | 15 | | ALL |
| 4501WL | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 16 | | D00449 | | 16 | | ALL |
| 4501WN | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 18 | | D00449 | | 18 | | ALL |
| 4501WO | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 17 | | D00449 | | 17 | | ALL |
| 4501WR | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 11 | | D00449 | | 11 | | ALL |
| 4501WY | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 13 | | D00449 | | 13 | | ALL |
| 4501Y | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 3 | | D00449 | | 3 | | ALL |
| 4501YG | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 35 | | D00449 | | 35 | | ALL |
| 4501YK | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 36 | | D00449 | | 36 | | ALL |
| 4501YL | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 37 | | D00449 | | 37 | | ALL |
| 4501YO | 24 | VA | AA | | 0-0 | 23-51-21 | D41555P | | 38 | | D00449 | | 38 | | ALL |
| W2339 | 286N2339 | | | FLIGHT-INTERPHONE-S/O, P61 TO E/E SHELF | | | | | | | | | | | |
| 4501 | 20 | VA | AA | | 40-0 | 23-51-51 | D41557P | | 20 | | D00453 | | 20 | | 115-199 |
| 4501AA | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 19 | | D00453 | | 19 | | 115-199 |
| 4501AB | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 27 | | D00453 | | 27 | | 115-199 |
| 4501AC | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 34 | | D00453 | | 34 | | 115-199 |
| 4501AD | 20 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 1 | | D00453 | | 1 | | 115-199 |
| 4501B | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 2 | | D00453 | | 2 | | 115-199 |
| 4501BG | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 29 | | D00453 | | 29 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2330

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|---|---------|----------|---------|-------|------|------|--------|-------|------|-------------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type |
| W2339 | 286N2339 | | | FLIGHT-INTERPHONE-S/O, P61 TO E/E SHELF (continued) | | | | | | | | | | | |
| 4501BK | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 30 | | D00453 | | 30 | | 115-199 |
| 4501BL | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 31 | | D00453 | | 31 | | 115-199 |
| 4501BN | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 33 | | D00453 | | 33 | | 115-199 |
| 4501BO | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 32 | | D00453 | | 32 | | 115-199 |
| 4501BY | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 28 | | D00453 | | 28 | | 115-199 |
| 4501G | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 4 | | D00453 | | 4 | | 115-199 |
| 4501K | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 5 | | D00453 | | 5 | | 115-199 |
| 4501L | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 6 | | D00453 | | 6 | | 115-199 |
| 4501N | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 8 | | D00453 | | 8 | | 115-199 |
| 4501O | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 7 | | D00453 | | 7 | | 115-199 |
| 4501P | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 9 | | D00453 | | 9 | | 115-199 |
| 4501RG | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 22 | | D00453 | | 22 | | 115-199 |
| 4501RK | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 23 | | D00453 | | 23 | | 115-199 |
| 4501RL | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 24 | | D00453 | | 24 | | 115-199 |
| 4501RN | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 26 | | D00453 | | 26 | | 115-199 |
| 4501RO | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 25 | | D00453 | | 25 | | 115-199 |
| 4501RY | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 21 | | D00453 | | 21 | | 115-199 |
| 4501W | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 10 | | D00453 | | 10 | | 115-199 |
| 4501WB | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 12 | | D00453 | | 12 | | 115-199 |
| 4501WG | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 14 | | D00453 | | 14 | | 115-199 |
| 4501WK | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 15 | | D00453 | | 15 | | 115-199 |
| 4501WL | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 16 | | D00453 | | 16 | | 115-199 |
| 4501WN | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 18 | | D00453 | | 18 | | 115-199 |
| 4501WO | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 17 | | D00453 | | 17 | | 115-199 |
| 4501WR | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 11 | | D00453 | | 11 | | 115-199 |
| 4501WY | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 13 | | D00453 | | 13 | | 115-199 |
| 4501Y | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 3 | | D00453 | | 3 | | 115-199 |
| 4501YG | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 35 | | D00453 | | 35 | | 115-199 |
| 4501YK | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 36 | | D00453 | | 36 | | 115-199 |
| 4501YL | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 37 | | D00453 | | 37 | | 115-199 |
| 4501YO | 24 | VA | AA | | 0-0 | 23-51-51 | D41557P | | 38 | | D00453 | | 38 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2330

Page 6 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2341 | 286N2341 | | | FLIGHT-INTERPHONE-OBS, P17 TO E4-3 SHELF | | | | | | | | | | | |
| 4501 | 20 | VA | AA | | 44-0 | 23-51-41 | D41559P | 20 | | | D00457 | 20 | | | ALL |
| 4501AA | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 19 | | | D00457 | 19 | | | ALL |
| 4501AB | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 27 | | | D00457 | 27 | | | ALL |
| 4501AC | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 34 | | | D00457 | 34 | | | ALL |
| 4501AD | 20 | VA | AA | | 0-0 | 23-51-41 | D41559P | 1 | | | D00457 | 1 | | | ALL |
| 4501B | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 2 | | | D00457 | 2 | | | ALL |
| 4501BG | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 29 | | | D00457 | 29 | | | ALL |
| 4501BK | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 30 | | | D00457 | 30 | | | ALL |
| 4501BL | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 31 | | | D00457 | 31 | | | ALL |
| 4501BN | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 33 | | | D00457 | 33 | | | ALL |
| 4501BO | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 32 | | | D00457 | 32 | | | ALL |
| 4501BY | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 28 | | | D00457 | 28 | | | ALL |
| 4501G | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 4 | | | D00457 | 4 | | | ALL |
| 4501K | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 5 | | | D00457 | 5 | | | ALL |
| 4501L | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 6 | | | D00457 | 6 | | | ALL |
| 4501N | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 8 | | | D00457 | 8 | | | ALL |
| 4501O | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 7 | | | D00457 | 7 | | | ALL |
| 4501P | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 9 | | | D00457 | 9 | | | ALL |
| 4501RG | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 22 | | | D00457 | 22 | | | ALL |
| 4501RK | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 23 | | | D00457 | 23 | | | ALL |
| 4501RL | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 24 | | | D00457 | 24 | | | ALL |
| 4501RN | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 26 | | | D00457 | 26 | | | ALL |
| 4501RO | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 25 | | | D00457 | 25 | | | ALL |
| 4501RY | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 21 | | | D00457 | 21 | | | ALL |
| 4501W | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 10 | | | D00457 | 10 | | | ALL |
| 4501WB | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 12 | | | D00457 | 12 | | | ALL |
| 4501WG | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 14 | | | D00457 | 14 | | | ALL |
| 4501WK | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 15 | | | D00457 | 15 | | | ALL |
| 4501WL | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 16 | | | D00457 | 16 | | | ALL |
| 4501WN | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 18 | | | D00457 | 18 | | | ALL |
| 4501WO | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 17 | | | D00457 | 17 | | | ALL |
| 4501WR | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 11 | | | D00457 | 11 | | | ALL |
| 4501WY | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 13 | | | D00457 | 13 | | | ALL |
| 4501Y | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 3 | | | D00457 | 3 | | | ALL |
| 4501YG | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 35 | | | D00457 | 35 | | | ALL |
| 4501YK | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 36 | | | D00457 | 36 | | | ALL |
| 4501YL | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 37 | | | D00457 | 37 | | | ALL |
| 4501YO | 24 | VA | AA | | 0-0 | 23-51-41 | D41559P | 38 | | | D00457 | 38 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2340

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|---------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2343 | 286N2343 | | | HF-L CONTROL, P5 TO E4-3 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 8-0 | 33-13-31 | D00311 | | 1 | | TB0114Z | 7 | BJ | | 001-099 |
| 0001 | 20 | | GA | | 7-0 | 33-13-31 | D00311 | | 1 | | TB0114Z | 7 | BJ | | 115-199 |
| 0002 | 20 | | GA | | 8-0 | 33-13-31 | D00311 | | 2 | | TB0114Z | 9 | BJ | | 001-099 |
| 0002 | 20 | | GA | | 7-0 | 33-13-31 | D00311 | | 2 | | TB0114Z | 9 | BJ | | 115-199 |
| 0003 | 22 | | GA | | 48-0 | 23-11-11 | D00311 | | 13 | | D42031P | 3 | | | 001-099 |
| 0003 | 22 | | GA | | 142-0 | 23-11-11 | D00311 | | 13 | | D41797P | 3 | | | 115-199 |
| 0004 | 22 | | GA | | 48-0 | 23-11-11 | D00311 | | 14 | | D42031P | 4 | | | 001-099 |
| 0004 | 22 | | GA | | 142-0 | 23-11-11 | D00311 | | 14 | | D41797P | 4 | | | 115-199 |
| 0005 | 22 | | GA | | 48-0 | 23-11-11 | D00311 | | 5 | | D42031P | 5 | | | 001-099 |
| 0005 | 22 | | GA | | 142-0 | 23-11-11 | D00311 | | 5 | | D41797P | 5 | | | 115-199 |
| 0006 | 22 | | GA | | 48-0 | 23-11-11 | D00311 | | 12 | | D42031P | 6 | | | 001-099 |
| 0006 | 22 | | GA | | 142-0 | 23-11-11 | D00311 | | 12 | | D41797P | 6 | | | 115-199 |
| 0007 | 22 | | GA | | 48-0 | 23-11-11 | D00311 | | 7 | | D42031P | 7 | | | 001-099 |
| 0007 | 22 | | GA | | 142-0 | 23-11-11 | D00311 | | 7 | | D41797P | 7 | | | 115-199 |
| 0008 | 22 | | GA | | 48-0 | 23-11-11 | D00311 | | 8 | | D42031P | 8 | | | 001-099 |
| 0008 | 22 | | GA | | 142-0 | 23-11-11 | D00311 | | 8 | | D41797P | 8 | | | 115-199 |
| 0009 | 20 | | GA | | 7-0 | 23-11-11 | D00311 | | 3 | | TB0111X | A001 | BJ | | 001-099 |
| 0009 | 20 | | GA | | 6-0 | 23-11-11 | D00311 | | 3 | | TB0111X | A001 | BJ | | 115-199 |
| 0010 | 20 | | GA | | 5-0 | 23-11-11 | D00311 | | 4 | | GD00600 | AC.. | 2 | | 001-099 |
| 0010 | 20 | | GA | | 4-0 | 23-11-11 | D00311 | | 4 | | GD00600 | AC.. | 2 | | 115-199 |
| 0011 | 22 | | GA | | 0-6 | 23-11-11 | D00311 | | 11 | | SM00001 | | 9 | | ALL |
| 0012 | 22 | | GA | | 0-6 | 23-11-11 | D00311 | | 15 | | SM00001 | | 9 | | ALL |
| 0013 | 20 | | GA | | 5-0 | 23-11-11 | SM00001 | | 9 | | GD00600 | ST.. | 2 | | 001-099 |
| 0013 | 20 | | GA | | 4-0 | 23-11-11 | SM00001 | | 9 | | GD00600 | ST.. | 2 | | 115-199 |
| 2501B | 24 | | G2 | AA | 48-0 | 23-11-11 | D00311 | | 10 | | D42031P | | 10 | | 001-099 |
| 2501B | 24 | | G2 | AA | 142-0 | 23-11-11 | D00311 | | 10 | | D41797P | | 10 | | 115-199 |
| 2501R | 24 | | G2 | AA | 0-0 | 23-11-11 | D00311 | | 9 | | D42031P | | 9 | | 001-099 |
| 2501R | 24 | | G2 | AA | 0-0 | 23-11-11 | D00311 | | 9 | | D41797P | | 9 | | 115-199 |
| 2501Z | | | | AA | 0-0 | 23-11-11 | SM00001 | | 9 | | D42031P | | 11 | | 001-099 |
| 2501Z | | | | AA | 0-0 | 23-11-11 | SM00001 | | 9 | | D41797P | | 11 | | 115-199 |
| W2344 | 286N2344 | | | P11 AND P6 TO P71 - POWER DIST CAT L | | | | | | | | | | | |
| 0001 | 12 | | GA | | 31-10 | 24-51-15 | TB5019 | | 4 | E | * | D40452P | 1 | | 001-099 |
| 0001 | 12 | | GA | | 32-0 | 24-51-15 | TB5019 | | 4 | E | * | D40452P | 1 | | 115-199 |
| 0002 | 12 | | GA | | 31-10 | 24-51-15 | TB5019 | | 5 | E | * | D40452P | 2 | | 001-099 |
| 0002 | 12 | | GA | | 32-0 | 24-51-15 | TB5019 | | 5 | E | * | D40452P | 2 | | 115-199 |
| 0003 | 12 | | GA | | 31-10 | 24-51-15 | TB5019 | | 6 | E | * | D40452P | 3 | | 001-099 |
| 0003 | 12 | | GA | | 32-0 | 24-51-15 | TB5019 | | 6 | E | * | D40452P | 3 | | 115-199 |
| 0004 | 14 | | GA | | 31-10 | 24-51-15 | TB5019 | | 1 | E | | D40452P | 4 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2340

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2344 | 286N2344 | | | P11 AND P6 TO P71 - POWER DIST CAT L (continued) | | | | | | | | | | | |
| 0004 | 14 | | GA | | 32-0 | 24-51-15 | TB5019 | 1 | E | | D40452P | 4 | | | 115-199 |
| 0005 | 14 | | GA | | 31-10 | 24-51-15 | TB5019 | 2 | E | | D40452P | 5 | | | 001-099 |
| 0005 | 14 | | GA | | 32-0 | 24-51-15 | TB5019 | 2 | E | | D40452P | 5 | | | 115-199 |
| 0006 | 14 | | GA | | 31-10 | 24-51-15 | TB5019 | 3 | E | | D40452P | 6 | | | 001-099 |
| 0006 | 14 | | GA | | 32-0 | 24-51-15 | TB5019 | 3 | E | | D40452P | 6 | | | 115-199 |
| 0007 | 12 | | GA | | 17-0 | 24-51-15 | TB5001 | 9 | E | | TB5019 | 4 | E | * | ALL |
| 0008 | 12 | | GA | | 17-0 | 24-51-15 | TB5001 | 10 | E | | TB5019 | 5 | E | * | ALL |
| 0009 | 12 | | GA | | 17-0 | 24-51-15 | TB5001 | 11 | E | | TB5019 | 6 | E | * | ALL |
| 0010 | 18 | | GA | | 17-0 | 24-51-15 | TB5001 | 12 | E | | TB5019 | 7 | E | | ALL |
| 0011 | 16 | | GA | | 32-1 | 24-51-72 | TB5019 | 10 | E | | D40416P | 5 | | | 001-099 |
| 0011 | 16 | | GA | | 33-0 | 24-51-72 | TB5019 | 10 | E | | D40416P | 5 | | | 115-199 |
| 0012 | 16 | | GA | | 32-1 | 24-51-72 | TB5019 | 9 | E | | D40416P | 4 | | | 001-099 |
| 0012 | 16 | | GA | | 33-0 | 24-51-72 | TB5019 | 9 | E | | D40416P | 4 | | | 115-199 |
| 0013 | 16 | | GA | | 32-1 | 24-51-72 | TB5019 | 8 | E | | D40416P | 3 | | | 001-099 |
| 0013 | 16 | | GA | | 33-0 | 24-51-72 | TB5019 | 8 | E | | D40416P | 3 | | | 115-199 |
| 0014 | 12 | | GA | | 45-10 | 24-51-72 | D40452P | 10 | | | TB5003 | 10 | E | | 001-099 |
| 0014 | 12 | | GA | | 47-0 | 24-51-72 | D40452P | 10 | | | TB5003 | 10 | E | | 115-199 |
| 0015 | 12 | | GA | | 45-10 | 24-51-72 | D40452P | 9 | | | TB5003 | 9 | E | | 001-099 |
| 0015 | 12 | | GA | | 47-0 | 24-51-72 | D40452P | 9 | | | TB5003 | 9 | E | | 115-199 |
| 0016 | 12 | | GA | | 45-10 | 24-51-72 | D40452P | 8 | | | TB5003 | 8 | E | | 001-099 |
| 0016 | 12 | | GA | | 47-0 | 24-51-72 | D40452P | 8 | | | TB5003 | 8 | E | | 115-199 |
| 0017 | 22 | | GA | | 33-5 | 24-25-11 | TB0121X | A018 | BJ | | D40416P | 1 | | | 001-099 |
| 0017 | 22 | | GA | | 34-0 | 24-25-11 | TB0121X | A018 | BJ | | D40416P | 1 | | | 115-199 |
| 0018 | 22 | | GA | | 33-5 | 34-22-81 | TB0121X | A019 | BJ | | D40416P | 6 | | | 001-099 |
| 0018 | 22 | | GA | | 34-0 | 34-22-83 | TB0121X | A019 | BJ | | D40416P | 6 | | | 115-199 |
| W2345 | 286N2345 | | | HF-R CONTROL, P5 TO E3-2 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 33-13-31 | D00313 | 1 | | | TB0114Z | 7 | BJ | | 001-099 |
| 0001 | 20 | | GA | | 8-0 | 33-13-31 | D00313 | 1 | | | TB0114Z | 7 | BJ | | 115-199 |
| 0002 | 20 | | GA | | 5-0 | 33-13-31 | D00313 | 2 | | | TB0114Z | 9 | BJ | | 001-099 |
| 0002 | 20 | | GA | | 8-0 | 33-13-31 | D00313 | 2 | | | TB0114Z | 9 | BJ | | 115-199 |
| 0003 | 22 | | GA | | 56-0 | 23-11-21 | D00313 | 13 | | | D42045P | 3 | | | 001-099 |
| 0003 | 22 | | GA | | 150-0 | 23-11-21 | D00313 | 13 | | | D41747P | 3 | | | 115-199 |
| 0004 | 22 | | GA | | 56-0 | 23-11-21 | D00313 | 14 | | | D42045P | 4 | | | 001-099 |
| 0004 | 22 | | GA | | 150-0 | 23-11-21 | D00313 | 14 | | | D41747P | 4 | | | 115-199 |
| 0005 | 22 | | GA | | 56-0 | 23-11-21 | D00313 | 5 | | | D42045P | 5 | | | 001-099 |
| 0005 | 22 | | GA | | 150-0 | 23-11-21 | D00313 | 5 | | | D41747P | 5 | | | 115-199 |
| 0006 | 22 | | GA | | 56-0 | 23-11-21 | D00313 | 12 | | | D42045P | 6 | | | 001-099 |
| 0006 | 22 | | GA | | 150-0 | 23-11-21 | D00313 | 12 | | | D41747P | 6 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2340

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|---|-------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|------------------|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2345 | 286N2345 | HF-R CONTROL, P5 TO E3-2 (continued) | | | | | | | | | | | | | |
| 0007 | 22 | GA | | 56-0 | 23-11-21 | D00313 | | 7 | D42045P | | 7 | | | 001-099 | |
| 0007 | 22 | GA | | 150-0 | 23-11-21 | D00313 | | 7 | D41747P | | 7 | | | 115-199 | |
| 0008 | 22 | GA | | 56-0 | 23-11-21 | D00313 | | 8 | D42045P | | 8 | | | 001-099 | |
| 0008 | 22 | GA | | 150-0 | 23-11-21 | D00313 | | 8 | D41747P | | 8 | | | 115-199 | |
| 0009 | 20 | GA | | 5-0 | 23-11-21 | D00313 | | 3 | TB0113X | C001 | BJ | | | 001-099 | |
| 0009 | 20 | GA | | 8-0 | 23-11-21 | D00313 | | 3 | TB0113X | C001 | BJ | | | 115-199 | |
| 0010 | 20 | GA | | 5-0 | 23-11-21 | D00313 | | 4 | GD00604 | AC.. | 2 | | | 001-099 | |
| 0010 | 20 | GA | | 4-0 | 23-11-21 | D00313 | | 4 | GD00604 | AC.. | 2 | | | 115-199 | |
| 0011 | 22 | GA | | 0-6 | 23-11-21 | D00313 | | 11 | SM00001 | | 9 | | | ALL | |
| 0012 | 22 | GA | | 0-6 | 23-11-21 | D00313 | | 15 | SM00001 | | 9 | | | ALL | |
| 0013 | 20 | GA | | 4-0 | 23-11-21 | SM00001 | | | GD00604 | ST.. | 2 | | | ALL | |
| 2501B | 24 | G2 | AA | 56-0 | 23-11-21 | D00313 | | 10 | D42045P | | 10 | | | 001-099 | |
| 2501B | 24 | G2 | AA | 150-0 | 23-11-21 | D00313 | | 10 | D41747P | | 10 | | | 115-199 | |
| 2501R | 24 | G2 | AA | 0-0 | 23-11-21 | D00313 | | 9 | D42045P | | 9 | | | 001-099 | |
| 2501R | 24 | G2 | AA | 0-0 | 23-11-21 | D00313 | | 9 | D41747P | | 9 | | | 115-199 | |
| 2501Z | | | AA | 0-0 | 23-11-21 | SM00001 | | 9 | D42045P | | 11 | | | 001-099 | |
| 2501Z | | | AA | 0-0 | 23-11-21 | SM00001 | | 9 | D41747P | | 11 | | | 115-199 | |
| W2346 | 286N2346 | P11 AND P6 TO P71 - POWER DIST CAT R | | | | | | | | | | | | | |
| 0001 | 18 | GA | | 31-0 | 24-51-25 | D40460P | | 1 | TB5025 | | 1 | E | | 001-002, 115-199 | |
| 0001 | 12 | GA | | 30-6 | 24-51-25 | D40460P | | 1 | TB5025 | | 1 | E | | 003-099 | |
| 0002 | 18 | GA | | 31-0 | 24-51-25 | D40460P | | 2 | TB5025 | | 2 | E | | 001-002, 115-199 | |
| 0002 | 12 | GA | | 30-5 | 24-51-25 | D40460P | | 2 | TB5025 | | 2 | E | | 003-099 | |
| 0003 | 18 | GA | | 31-0 | 24-51-25 | D40460P | | 3 | TB5025 | | 3 | E | | 001-002, 115-199 | |
| 0003 | 12 | GA | | 30-4 | 24-51-25 | D40460P | | 3 | TB5025 | | 3 | E | | 003-099 | |
| 0004 | 12 | GA | | 31-0 | 24-51-25 | D40460P | | 4 | TB5025 | | 4 | E | * | 001-002, 115-199 | |
| 0004 | 12 | GA | | 30-3 | 24-51-25 | D40460P | | 4 | TB5025 | | 4 | E | * | 003-099 | |
| 0005 | 12 | GA | | 31-0 | 24-51-25 | D40460P | | 5 | TB5025 | | 5 | E | * | 001-002, 115-199 | |
| 0005 | 12 | GA | | 30-2 | 24-51-25 | D40460P | | 5 | TB5025 | | 5 | E | * | 003-099 | |
| 0006 | 12 | GA | | 38-0 | 24-51-25 | TB5006 | | 10 | E | | 6 | | | 001-002, 115-199 | |
| 0006 | 12 | GA | | 30-1 | 24-51-25 | TB5025 | | 6 | E | * | 6 | | | 003-099 | |
| 0007 | 12 | GA | | 13-0 | 24-51-25 | TB5006 | | 11 | E | | 5 | E | * | 001-002 | |
| 0007 | 12 | GA | | 12-6 | 24-51-25 | TB5006 | | 11 | E | | 5 | E | * | 003-099 | |
| 0007 | 12 | GA | | 14-0 | 24-51-25 | TB5006 | | 11 | E | | 5 | E | * | 115-199 | |
| 0008 | 12 | GA | | 13-0 | 24-51-25 | TB5006 | | 12 | E | | 4 | E | * | 001-002, 115-199 | |
| 0008 | 12 | GA | | 12-8 | 24-51-25 | TB5006 | | 12 | E | | 4 | E | * | 003-099 | |
| 0009 | 20 | GA | | 32-0 | 24-25-11 | TB0121X | A017 | BJ | D40460P | | 9 | | | ALL | |
| 0010 | 24 | GK | | 11-0 | 33-51-11 | D40460P | | 8 | SP01280 | | 9 | | | 001-002, 115-199 | |
| 0010 | 24 | GK | | 10-11 | 33-51-11 | D40460P | | 8 | SP01280 | | 9 | | | 003-099 | |

WIRE LIST

D280N032

91-21-11

Section W2340

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2346 | 286N2346 | | | P11 AND P6 TO P71 - POWER DIST CAT R (continued) | | | | | | | | | | | |
| 0018 | 18 | | GA | | 10-11 | 28-22-11 | D40460P | 10 | | | SP01912 | | 9 | | 003-099 |
| 0019 | 18 | | GA | | 10-11 | 28-22-11 | D40460P | 11 | | | SP01914 | | 9 | | 003-099 |
| 0020 | 12 | | GA | | 12-4 | 24-51-25 | TB5025 | 6 | E | * | TB5006 | 10 | E | | 003-099 |
| W2348 | 286N2348 | | | P71 TO P36 - POWER DIST CAT S | | | | | | | | | | | |
| 0001 | 22 | | GA | | 8-0 | 24-25-11 | D40292P | 1 | | | D40270P | 1 | | | ALL |
| 0002 | 22 | | GA | | 8-0 | 24-25-11 | D40292P | 2 | | | D40270P | 2 | | | ALL |
| 0003 | 24 | | GK | | 8-0 | 24-25-13 | D40292P | 3 | | | D40270P | 3 | | | 001-002, 115-199 |
| 0004 | 24 | | GK | | 8-0 | 24-25-13 | D40292P | 4 | | | D40270P | 4 | | | ALL |
| 0005 | 24 | | GK | | 8-0 | 24-25-13 | D40292P | 5 | | | D40270P | 5 | | | ALL |
| 0006 | 24 | | GK | | 8-0 | 24-25-13 | D40292P | 6 | | | D40270P | 6 | | | ALL |
| 0007 | 22 | | GA | | 8-0 | 21-58-15 | D40292P | 7 | | | D40270P | 7 | | | 001-002, 115-199 |
| 0013 | 22 | | GA | | 8-0 | 24-25-11 | D40292P | 12 | | | D40270P | 3 | | | 003-099 |
| 0020 | 22 | | GA | | 8-0 | 24-25-11 | D40270P | 8 | | | D40292P | 8 | | | 001-002, 115-199 |
| 0026 | 22 | | GA | | 8-0 | 24-25-11 | D40270P | 7 | | | D40292P | 16 | | | 003-099 |
| 0029 | 20 | | GA | | 8-0 | SPARE | D40270P | 8 | | | D40292P | 17 | | | 003-099 |
| 0038 | 24 | | GK | | 8-0 | 24-25-13 | D40270P | 15 | | | D40292P | 10 | | | 003-099 |
| 0039 | 20 | | GA | | 8-0 | 24-31-11 | D40270P | 16 | | | D40292P | 11 | | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W2340

Page 5 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2350 | | 286N2350 | | | | P11 TO E/E BAY - POWER DISTR CAT L(A) | | | | | | | | | |
| 0002 | 22 | GA | | | 50-0 | SPARE | D40610P | | 2 | | D40686P | | 2 | | 115-199 |
| 0003 | 22 | GA | | | 41-0 | 31-31-01 | D40612P | | 2 | | D40678P | | 3 | | 001-099 |
| 0003 | 22 | GA | | | 41-0 | 31-31-11 | D40612P | | 2 | | D40678P | | 3 | | 115-199 |
| 0004 | 22 | GA | | | 41-0 | 31-31-01 | D40612P | | 6 | | D40678P | | 4 | | 001-099 |
| 0004 | 22 | GA | | | 41-0 | 31-31-11 | D40612P | | 6 | | D40678P | | 4 | | 115-199 |
| 0005 | 22 | GA | | | 40-0 | SPARE | D40610P | | 49 | | D40676P | | 1 | | ALL |
| 0007 | 24 | GK | | | 51-0 | 79-32-11 | D40612P | | 27 | | D40684P | | 3 | | 001-099 |
| 0007 | 24 | GK | | | 52-0 | 79-32-11 | D40612P | | 27 | | D40684P | | 3 | | 115-199 |
| 0008 | 24 | GK | | | 51-0 | 27-28-11 | D40612P | | 8 | | D40684P | | 2 | | 001-099 |
| 0008 | 24 | GK | | | 52-0 | 27-28-11 | D40612P | | 8 | | D40684P | | 2 | | 115-199 |
| 0009 | 22 | GA | | | 51-0 | 27-28-13 | D40612P | | 9 | | D40684P | | 1 | | 001-099 |
| 0009 | 22 | GA | | | 52-0 | 27-28-13 | D40612P | | 9 | | D40684P | | 1 | | 115-199 |
| 0010 | 22 | GA | | | 51-0 | 27-18-11 | D40612P | | 10 | | D40684P | | 10 | | 001-099 |
| 0010 | 22 | GA | | | 52-0 | 27-18-11 | D40612P | | 10 | | D40684P | | 10 | | 115-199 |
| 0011 | 22 | GA | | | 51-0 | 27-38-11 | D40612P | | 11 | | D40684P | | 11 | | 001-099 |
| 0011 | 22 | GA | | | 52-0 | 27-38-11 | D40612P | | 11 | | D40684P | | 11 | | 115-199 |
| 0012Y | 22 | QB | | | 40-0 | 27-41-11 | D40610P | | 12 | | D40676P | | 12 | | ALL |
| 0013 | 20 | GA | | | 40-0 | 34-21-11 | D40610P | | 13 | | SP01032 | | 9 | | 001-099 |
| 0013 | 20 | GA | | | 37-0 | 34-21-11 | D40610P | | 13 | | SP01032 | | 9 | | 115-199 |
| 0014 | 20 | GA | | | 37-0 | 22-31-12 | D40610P | | 14 | | D40674P | | 10 | | 001-099 |
| 0014 | 20 | GA | | | 36-0 | 22-31-12 | D40610P | | 14 | | D40674P | | 14 | | 115-199 |
| 0015 | 20 | GA | | | 37-0 | 22-31-12 | D40610P | | 15 | | D40674P | | 11 | | 001-099 |
| 0015 | 20 | GA | | | 36-0 | 22-31-12 | D40610P | | 15 | | D40674P | | 15 | | 115-199 |
| 0016 | 20 | GA | | | 37-0 | 22-31-11 | D40610P | | 16 | | D40674P | | 6 | | 001-099 |
| 0016 | 20 | GA | | | 36-0 | 22-31-11 | D40610P | | 16 | | D40674P | | 6 | | 115-199 |
| 0017 | 20 | GA | | | 36-0 | 22-11-11 | D40610P | | 17 | | D41910P | | 7 | | ALL |
| 0018 | 22 | GA | | | 36-0 | SPARE | D40610P | | 18 | | D41910P | | 6 | | ALL |
| 0019 | 24 | GK | | | 36-0 | 34-22-16 | D40610P | | 19 | | D41910P | | 2 | | ALL |
| 0020 | 20 | GA | | | 36-0 | 22-11-12 | D40610P | | 20 | | D41910P | | 10 | | ALL |
| 0021 | 20 | GA | | | 36-0 | 22-11-12 | D40610P | | 21 | | D41910P | | 11 | | ALL |
| 0022 | 22 | GA | | | 36-0 | 34-61-11 | D40610P | | 22 | | D41910P | | 3 | | ALL |
| 0023 | 22 | GA | | | 36-0 | 34-25-11 | D40610P | | 3 | | D40674P | | 3 | | 001, 003-099, 115-199 |
| 0024 | 22 | GA | | | 37-0 | 34-46-11 | D40610P | | 24 | | D40674P | | 4 | | 001-099 |
| 0024 | 22 | GA | | | 36-0 | 34-46-11 | D40610P | | 24 | | D40674P | | 4 | | 115-199 |
| 0025 | 22 | GA | | | 36-0 | 77-11-11 | D40612P | | 3 | | D40674P | | 1 | | ALL |
| 0026 | 22 | GA | | | 50-0 | 23-21-11 | D40610P | | 26 | | D40686P | | 1 | | ALL |
| 0027 | 22 | GA | | | 51-0 | 34-33-11 | D40610P | | 27 | | D41882P | | 1 | | ALL |
| 0028 | 24 | GK | | | 45-0 | 32-41-11 | D40680P | | 10 | | D40612P | | 14 | | 001-099 |
| 0028 | 24 | GK | | | 44-0 | 32-41-11 | D40680P | | 10 | | D40612P | | 14 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| Wire No. | GA | CO | TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2350 | 286N2350 | | | P11 TO E/E BAY - POWER DISTR CAT L(A) (continued) | | | | | | | | | | | | |
| 0029 | 22 | | GA | | 41-0 | 34-55-11 | D40610P | 29 | | | | D40678P | 9 | | | 001-099 |
| 0029 | 22 | | GA | | 41-0 | SPARE | D40610P | 29 | | | | D40678P | 9 | | | 115-199 |
| 0031 | 24 | | GK | | 36-0 | 34-22-16 | D40610P | 31 | | | | D41910P | 1 | | | 001, 003-008 |
| 0031 | 24 | | GK | | 36-0 | SPARE | D40610P | 31 | | | | D41910P | 1 | | | 002, 009-099, 115-199 |
| 0032 | 22 | | GA | | 41-0 | 31-31-01 | D40612P | 30 | | | | D40678P | 6 | | | 001-099 |
| 0033 | 20 | | GA | | 36-0 | 34-43-11 | D40610P | 33 | | | | D41910P | 5 | | | ALL |
| 0034 | 24 | | GK | | 52-0 | SPARE | D40610P | 34 | | | | D40684P | 6 | | | 115-199 |
| 0036 | 24 | | GK | | 51-0 | 27-51-41 | D40610P | 36 | | | | D41882P | 6 | | | 001-099 |
| 0036 | 22 | | GA | | 51-0 | 27-51-41 | D40610P | 36 | | | | D41882P | 6 | | | 115-199 |
| 0037 | 24 | | GK | | 36-0 | 34-12-11 | D40610P | 37 | | | | D41910P | 13 | | | ALL |
| 0038 | 24 | | GK | | 36-0 | 34-12-11 | D40610P | 38 | | | | D41910P | 9 | | | ALL |
| 0039 | 24 | | GK | | 37-0 | 34-22-36 | D40610P | 39 | | | | D40674P | 9 | | | 001-099 |
| 0039 | 24 | | GK | | 36-0 | 34-22-36 | D40610P | 39 | | | | D40674P | 9 | | | 115-199 |
| 0040 | 16 | | GA | | 52-0 | 23-12-31 | D40610P | 40 | 16 | | | D40688J | 10 | | | 001-099 |
| 0041 | 22 | | GA | | 49-0 | SPARE | D40610P | 41 | | | | D41422P | 8 | | | ALL |
| 0042 | 22 | | GA | | 60-0 | 28-22-11 | D40612P | 12 | | | | D41422P | 12 | | | 001-099 |
| 0042 | 22 | | GA | | 49-0 | 28-22-11 | D40612P | 12 | | | | D41422P | 12 | | | 115-199 |
| 0043 | 24 | | GK | | 51-0 | 27-51-41 | D40610P | 43 | | | | D41882P | 9 | | | 001-099 |
| 0043 | 22 | | GA | | 51-0 | 27-51-41 | D40610P | 43 | | | | D41882P | 9 | | | 115-199 |
| 0045 | 22 | | GA | | 45-0 | SPARE | D40612P | 45 | | | | D40680P | 5 | | | 001-099 |
| 0045 | 22 | | GA | | 44-0 | SPARE | D40612P | 45 | | | | D40680P | 5 | | | 115-199 |
| 0046 | 24 | | GK | | 164-0 | 32-46-11 | D40612P | 26 | | | | D42208P | 6 | | | 115-199 |
| 0047 | 24 | | GK | | 51-0 | 27-51-41 | D40610P | 47 | | | | D41882P | 8 | | | 001-099 |
| 0047 | 22 | | GA | | 51-0 | 27-51-41 | D40610P | 47 | | | | D41882P | 8 | | | 115-199 |
| 0048 | 20 | | GA | | 166-0 | 21-51-23 | D40612P | 48 | | | | D42216P | 8 | | | 115-199 |
| 0049 | 20 | | GA | | 166-0 | SPARE | D40612P | 49 | | | | D42216P | 9 | | | 115-199 |
| 0051 | 20 | | GA | | 50-0 | 23-11-11 | D40610P | 51 | | | | D40686P | 4 | | | 001-099 |
| 0051 | 20 | | GA | | 163-0 | 23-11-11 | D40610P | 51 | | | | D41974P | 1 | | | 115-199 |
| 0052 | 20 | | GA | | 50-0 | 23-11-11 | D40610P | 52 | | | | D40686P | 5 | | | 001-099 |
| 0052 | 20 | | GA | | 163-0 | 23-11-11 | D40610P | 52 | | | | D41974P | 2 | | | 115-199 |
| 0053 | 20 | | GA | | 50-0 | 23-11-11 | D40610P | 53 | | | | D40686P | 6 | | | 001-099 |
| 0053 | 20 | | GA | | 163-0 | 23-11-11 | D40610P | 53 | | | | D41974P | 3 | | | 115-199 |
| 0057 | 22 | | GA | | 19-0 | 29-32-31 | D40684P | 7 | | | | SP00554 | | 9 | | 001-099 |
| 0057 | 22 | | GA | | 16-0 | 29-32-31 | D40684P | 7 | | | | SP00554 | | 9 | | 115-199 |
| 0059 | 22 | | GA | | 52-0 | 31-41-11 | D40612P | 19 | | | | D40684P | 5 | | | ALL |
| 0060 | 20 | | GA | | 37-0 | 34-45-01 | D40610P | 48 | | | | D41910P | 15 | | | 001-099 |
| 0060 | 20 | | GA | | 36-0 | 34-45-01 | D40610P | 48 | | | | D41910P | 15 | | | 115-199 |
| 0061 | 22 | | GA | | 37-0 | 34-31-11 | D40610P | 8 | | | | D40674P | 8 | | | 001-099 |
| 0061 | 22 | | GA | | 36-0 | 34-31-11 | D40610P | 8 | | | | D40674P | 8 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2350 | 286N2350 | | | P11 TO E/E BAY - POWER DISTR CAT L(A) (continued) | | | | | | | | | | | |
| 0063 | 22 | | GA | | 41-0 | 31-31-02 | D40612P | | 43 | | D40678P | | 8 | | 001-099 |
| 0065 | 22 | | GA | | 36-0 | 34-61-15 | D40612P | | 22 | | D41910P | | 16 | | 009-099 |
| 0066 | 22 | | GA | | 36-0 | SPARE | D40612P | | 46 | | D41910P | | 17 | | 009-099 |
| 0067 | 22 | | GA | | 36-0 | SPARE | D40612P | | 47 | | D41910P | | 18 | | 009-099 |
| 0080 | 20 | | GA | | 37-0 | 34-12-11 | D40610P | | 50 | | D41910P | | 8 | | 001-099 |
| 0080 | 20 | | GA | | 36-0 | 34-12-11 | D40610P | | 50 | | D41910P | | 8 | | 115-199 |
| 0081 | 20 | | GA | | 45-0 | 32-12-12 | D40612P | | 21 | | D40680P | | 6 | | 001-099 |
| 0081 | 20 | | GA | | 44-0 | 32-12-12 | D40612P | | 21 | | D40680P | | 6 | | 115-199 |
| 0082 | 24 | | GK | | 36-0 | SPARE | D40610P | | 32 | | D41910P | | 4 | | 001-099 |
| 0103 | 22 | | CQ | | 50-0 | 34-43-14 | D40610P | | 44 | | D00159B | J02 | | | 002 |
| 0105 | 22 | | GA | | 44-0 | SPARE | D40612P | | 5 | | D40680P | | 15 | | 115-199 |
| 0106 | 22 | | GA | | 41-0 | 27-48-11 | D40610P | | 46 | | D40676P | | 6 | | 001-099 |
| 0106 | 22 | | GA | | 40-0 | 27-48-11 | D40610P | | 46 | | D40676P | | 6 | | 115-199 |
| 0141 | 22 | | GA | | 143-0 | SPARE | D40680P | | 1 | | D42216P | | 1 | | 115-199 |
| 0142 | 22 | | GA | | 143-0 | 33-37-21 | D40680P | | 2 | | D42216P | | 2 | | 115-199 |
| 0201 | 22 | | GA | | 52-0 | 27-09-11 | D40610P | | 7 | | D40682P | | 3 | | ALL |
| 0202 | 22 | | GA | | 51-0 | 27-09-11 | D40610P | | 10 | | D40682P | | 2 | | 001-099 |
| 0202 | 22 | | GA | | 52-0 | 27-09-11 | D40610P | | 10 | | D40682P | | 2 | | 115-199 |
| 0203 | 20 | | GA | | 51-0 | 27-31-22 | D40612P | | 33 | | D40682P | | 4 | | 001-099 |
| 0203 | 20 | | GA | | 52-0 | 27-31-22 | D40612P | | 33 | | D40682P | | 4 | | 115-199 |
| 0205 | 18 | | GA | | 51-0 | SPARE | D40610P | | 23 | 18 | D41882P | | 10 | | 115-199 |
| 0323 | 22 | | GA | | 52-0 | SPARE | D40612P | | 23 | | D40684P | | 8 | | 115-199 |
| 0324 | 22 | | GA | | 52-0 | SPARE | D40612P | | 24 | | D40684P | | 9 | | 115-199 |
| 0406 | 24 | | GK | | 51-0 | SPARE | D40612P | | 16 | | D41422P | | 13 | | 001-099 |
| 0406 | 24 | | GK | | 49-0 | SPARE | D40612P | | 16 | | D41422P | | 13 | | 115-199 |
| 0444 | 24 | | GK | | 52-0 | 21-52-31 | D40612P | | 44 | | D40684P | | 14 | | ALL |
| 0501 | 22 | | GA | | 52-0 | 77-31-11 | D40612P | | 4 | | D40684P | | 4 | | ALL |
| 0502 | 22 | | GA | | 52-0 | SPARE | D40610P | | 5 | | D40684P | | 12 | | 115-199 |
| 0514 | 22 | | GA | | 49-0 | SPARE | D41422P | | 1 | | D40612P | | 34 | | 115-199 |
| 0520 | 22 | | GA | | 166-0 | SPARE | D40610P | | 6 | | D42216P | | 5 | | 115-199 |
| 0604 | 22 | | GA | | 41-0 | SPARE | D40610P | | 9 | | D40678P | | 1 | | 115-199 |
| 0605 | 22 | | GA | | 41-0 | SPARE | D40610P | | 11 | | D40678P | | 2 | | 115-199 |
| 0606 | 20 | | GA | | 41-0 | 22-41-11 | D40612P | | 18 | | D40678P | | 5 | | ALL |
| 0610 | 22 | | GA | | 51-0 | 29-31-11 | D41422P | | 2 | | D40612P | | 35 | | 001-099 |
| 0610 | 22 | | GA | | 49-0 | 29-31-11 | D41422P | | 2 | | D40612P | | 35 | | 115-199 |
| 0611 | 22 | | GA | | 49-0 | SPARE | D41422P | | 3 | | D40612P | | 36 | | 115-199 |
| 0612 | 22 | | GA | | 51-0 | SPARE | D41422P | | 4 | | D40612P | | 37 | | 001-099 |
| 0612 | 22 | | GA | | 49-0 | SPARE | D41422P | | 4 | | D40612P | | 37 | | 115-199 |
| 0613 | 22 | | GA | | 51-0 | SPARE | D41422P | | 5 | | D40612P | | 38 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2350 | 286N2350 | | | P11 TO E/E BAY - POWER DISTR CAT L(A) (continued) | | | | | | | | | | | |
| 0613 | 22 | | GA | | 49-0 | SPARE | D41422P | | 5 | | D40612P | | 38 | | 115-199 |
| 0703 | 22 | | GA | | 51-0 | SPARE | D40612P | | 25 | | D41882P | | 5 | | 115-199 |
| 0705 | 22 | | GA | | 51-0 | SPARE | D40612P | | 39 | | D41882P | | 4 | | 115-199 |
| 0706 | 22 | | GA | | 51-0 | SPARE | D40612P | | 40 | | D41882P | | 7 | | 115-199 |
| 0707 | 22 | | GA | | 49-0 | SPARE | D40612P | | 41 | | D41422P | | 6 | | 115-199 |
| 0708 | 22 | | GA | | 49-0 | SPARE | D40612P | | 42 | | D41422P | | 9 | | 115-199 |
| 0709 | 22 | | GA | | 49-0 | SPARE | D40612P | | 43 | | D41422P | | 10 | | 115-199 |
| 0710 | 22 | | GA | | 49-0 | SPARE | D40612P | | 32 | | D41422P | | 11 | | 115-199 |
| 0712 | 22 | | GA | | 163-0 | SPARE | D40612P | | 31 | | D41974P | | 14 | | 115-199 |
| 0716 | 22 | | GA | | 163-0 | SPARE | D40610P | | 25 | | D41974P | | 13 | | 115-199 |
| 0717 | 22 | | GA | | 50-0 | SPARE | D40610P | | 28 | | D40686P | | 3 | | 115-199 |
| 0728 | 22 | | GA | | 52-0 | SPARE | D40612P | | 29 | | D40682P | | 6 | | 115-199 |
| 0729 | 22 | | GA | | 52-0 | SPARE | D40612P | | 28 | | D40682P | | 7 | | ALL |
| 0730 | 22 | | GA | | 166-0 | SPARE | D42216P | | 3 | | D40610P | | 4 | | 115-199 |
| 0731 | 22 | | GA | | 166-0 | SPARE | D42216P | | 7 | | D40612P | | 7 | | 115-199 |
| 0732 | 22 | | GA | | 164-0 | SPARE | D42208P | | 4 | | D40610P | | 32 | | 115-199 |
| 0733 | 22 | | GA | | 164-0 | SPARE | D42208P | | 3 | | D40612P | | 13 | | 115-199 |
| 2048B | 24 | | GL | BZ | 123-0 | 21-61-51 | D42208P | | 2 | | D40678P | | 15 | | 001-099 |
| 2048R | 24 | | GL | BZ | 0-0 | 21-61-51 | D42208P | | 1 | | D40678P | | 14 | | 001-099 |
| W2351 | 286N2351 | | | E4-3 SHELF TO P05 PILOTS OVERHEAD PANEL | | | | | | | | | | | |
| 0001 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 1 | | D00333 | | 3 | | 001-099 |
| 0001 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 1 | | D00333 | | 3 | | 115-199 |
| 0002 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 2 | | D00333 | | 4 | | 001-099 |
| 0002 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 2 | | D00333 | | 4 | | 115-199 |
| 0003 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 3 | | D00333 | | 51 | | 001-099 |
| 0003 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 3 | | D00333 | | 51 | | 115-199 |
| 0004 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 4 | | D00333 | | 6 | | 001-099 |
| 0004 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 4 | | D00333 | | 6 | | 115-199 |
| 0005 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 5 | | D00333 | | 7 | | 001-099 |
| 0005 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 5 | | D00333 | | 7 | | 115-199 |
| 0006 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 6 | | D00333 | | 8 | | 001-099 |
| 0006 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 6 | | D00333 | | 8 | | 115-199 |
| 0007 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 7 | | D00333 | | 9 | | 001-099 |
| 0007 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 7 | | D00333 | | 9 | | 115-199 |
| 0008 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 8 | | D00333 | | 48 | | 001-099 |
| 0008 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 8 | | D00333 | | 48 | | 115-199 |
| 0009 | 24 | | GK | | 44-0 | 23-21-11 | D41541P | | 9 | | D00333 | | 11 | | 001-099 |
| 0009 | 24 | | GK | | 46-0 | 23-21-11 | D41541P | | 9 | | D00333 | | 11 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2351 | 286N2351 | | | E4-3 SHELF TO P05 PILOTS OVERHEAD PANEL (continued) | | | | | | | | | | | |
| 0010 | 24 | GK | | | 44-0 | 23-21-11 | D41541P | 10 | | | D00333 | 12 | | | 001-099 |
| 0010 | 24 | GK | | | 46-0 | 23-21-11 | D41541P | 10 | | | D00333 | 12 | | | 115-199 |
| 0011 | 24 | GK | | | 44-0 | 23-21-11 | D41541P | 11 | | | D00333 | 13 | | | 001-099 |
| 0011 | 24 | GK | | | 46-0 | 23-21-11 | D41541P | 11 | | | D00333 | 13 | | | 115-199 |
| 0012 | 24 | GK | | | 44-0 | 23-21-11 | D41541P | 12 | | | D00333 | 14 | | | 001-099 |
| 0012 | 24 | GK | | | 46-0 | 23-21-11 | D41541P | 12 | | | D00333 | 14 | | | 115-199 |
| 0013 | 24 | GK | | | 44-0 | 23-21-11 | D41541P | 13 | | | D00333 | 49 | | | 001-099 |
| 0013 | 24 | GK | | | 46-0 | 23-21-11 | D41541P | 13 | | | D00333 | 49 | | | 115-199 |
| 0014 | 24 | GK | | | 44-0 | 23-21-11 | D41541P | 14 | | | D00333 | 16 | | | 001-099 |
| 0014 | 24 | GK | | | 46-0 | 23-21-11 | D41541P | 14 | | | D00333 | 16 | | | 115-199 |
| 0015 | 24 | GK | | | 44-0 | 23-21-11 | D41541P | 15 | | | D00333 | 17 | | | 001-099 |
| 0015 | 24 | GK | | | 46-0 | 23-21-11 | D41541P | 15 | | | D00333 | 17 | | | 115-199 |
| 0016 | 24 | GK | | | 44-0 | 23-21-11 | D41541P | 16 | | | D00333 | 47 | | | 001-099 |
| 0016 | 24 | GK | | | 46-0 | 23-21-11 | D41541P | 16 | | | D00333 | 47 | | | 115-199 |
| 0017 | 22 | GA | | | 7-0 | 23-21-11 | D00333 | 35 | | | GD00608 | ST.. | 2 | | 001-099 |
| 0017 | 22 | GA | | | 5-0 | 23-21-11 | D00333 | 35 | | | GD00608 | ST.. | 2 | | 115-199 |
| 0018 | 20 | GA | | | 7-0 | 33-13-31 | D00333 | 1 | | | TB0114Z | 8 | BJ | | 001-099 |
| 0018 | 20 | GA | | | 5-0 | 33-13-31 | D00333 | 1 | | | TB0114Z | 8 | BJ | | 115-199 |
| 0019 | 20 | GA | | | 7-0 | 33-13-31 | D00333 | 2 | | | TB0114Z | 10 | BJ | | 001-099 |
| 0019 | 20 | GA | | | 5-0 | 33-13-31 | D00333 | 2 | | | TB0114Z | 10 | BJ | | 115-199 |
| 0020 | 22 | GA | | | 6-0 | 33-16-52 | D00333 | 40 | | | TB0116Z | 14 | BJ | | 001-099 |
| 0020 | 22 | GA | | | 7-0 | 33-16-52 | D00333 | 40 | | | TB0116Z | 14 | BJ | | 115-199 |
| 0021 | 22 | GA | | | 6-0 | 33-16-52 | D00333 | 41 | | | TB0116Z | 13 | BJ | | 001-099 |
| 0021 | 22 | GA | | | 7-0 | 33-16-52 | D00333 | 41 | | | TB0116Z | 13 | BJ | | 115-199 |
| 0022 | 20 | GA | | | 8-0 | 33-13-31 | D00001 | Y | | | TB0114Z | 11 | BJ | | 115-199 |
| 0023 | 20 | GA | | | 8-0 | 33-13-31 | D00001 | Z | | | TB0114Z | 10 | BJ | | 115-199 |
| 0028 | 22 | GA | | | 46-0 | 23-71-11 | D00001 | G | | | D41541P | 26 | | | 001-099 |
| 0028 | 22 | GA | | | 48-0 | 23-71-11 | D00001 | G | | | D41541P | 26 | | | 115-199 |
| 0029 | 22 | GA | | | 0-6 | 23-71-11 | D00001 | P | | | D00001 | G- | | | 001-099 |
| 0029 | 22 | GA | | | 0-6 | 23-71-11 | D00001 | P | | | SM00005 | | WI | | 115-199 |
| 0030 | 22 | GA | | | 0-6 | 23-71-11 | D00001 | N | | | D00001 | F- | | | 001-099 |
| 0030 | 22 | GA | | | 0-6 | 23-71-11 | D00001 | N | | | SM00004 | | WI | | 115-199 |
| 0031 | 22 | GA | | | 46-0 | 23-71-11 | D00001 | H | | | D41541P | 27 | | | 001-099 |
| 0031 | 22 | GA | | | 48-0 | 23-71-11 | D00001 | H | | | D41541P | 27 | | | 115-199 |
| 0032 | 22 | GA | | | 44-0 | 23-42-11 | D00333 | 20 | | | D41541P | 30 | | | 001-099 |
| 0032 | 22 | GA | | | 46-0 | 23-42-11 | D41541P | 30 | | | D00333 | 20 | | | 115-199 |
| 0033 | 22 | GA | | | 44-0 | 23-42-11 | D00333 | 23 | | | D41541P | 19 | | | 001-099 |
| 0033 | 22 | GA | | | 46-0 | 23-42-11 | D41541P | 19 | | | D00333 | 23 | | | 115-199 |
| 0034 | 22 | GA | | | 44-0 | 23-42-11 | D00333 | 26 | | | D41541P | 20 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2351 | 286N2351 | | | E4-3 SHELF TO P05 PILOTS OVERHEAD PANEL (continued) | | | | | | | | | | | |
| 0034 | 22 | | GA | | 46-0 | 23-42-11 | D41541P | 20 | | | D00333 | 26 | | | 115-199 |
| 0035 | 22 | | GA | | 44-0 | 23-42-11 | D00333 | 29 | | | D41541P | 33 | | | 001-099 |
| 0035 | 22 | | GA | | 46-0 | 23-42-11 | D41541P | 33 | | | D00333 | 29 | | | 115-199 |
| 0036 | 20 | | GA | | 46-0 | 23-71-11 | D00001 | F | | | D41541P | 21 | | | 001-099 |
| 0036 | 20 | | GA | | 48-0 | 23-71-11 | D00001 | F | | | D41541P | 21 | | | 115-199 |
| 0037 | 22 | | GA | | 46-0 | 23-71-11 | D00001 | C | | | D41541P | 22 | | | 001-099 |
| 0037 | 22 | | GA | | 48-0 | 23-71-11 | D00001 | C | | | D41541P | 22 | | | 115-199 |
| 0038 | 24 | | GK | | 46-0 | 23-71-11 | D00001 | B | | | D41541P | 36 | | | 001-099 |
| 0038 | 24 | | GK | | 48-0 | 23-71-11 | D00001 | B | | | D41541P | 36 | | | 115-199 |
| 0039 | 24 | | GK | | 46-0 | 23-71-11 | D00001 | D | | | D41541P | 37 | | | 001-099 |
| 0039 | 24 | | GK | | 48-0 | 23-71-11 | D00001 | D | | | D41541P | 37 | | | 115-199 |
| 0040 | 24 | | GK | | 46-0 | 23-71-11 | D00001 | E | | | D41541P | 38 | | | 001-099 |
| 0040 | 24 | | GK | | 48-0 | 23-71-11 | D00001 | E | | | D41541P | 38 | | | 115-199 |
| 0041 | 24 | | GK | | 46-0 | 23-71-11 | D00001 | A | | | D41541P | 39 | | | 001-099 |
| 0041 | 24 | | GK | | 48-0 | 23-71-11 | D00001 | A | | | D41541P | 39 | | | 115-199 |
| 0042 | 20 | | GA | | 0-6 | 23-71-11 | D00001 | R- | | | SM00001 | | WI | | 001-099 |
| 0042 | 20 | | GA | | 1-0 | 23-71-11 | D00001 | R- | | | SM00001 | | WI | | 115-199 |
| 0043 | 20 | | GA | | 0-6 | 23-71-11 | D00001 | Q- | | | SM00001 | | WI | | 001-099 |
| 0043 | 20 | | GA | | 1-0 | 23-71-11 | D00001 | Q- | | | SM00001 | | WI | | 115-199 |
| 0044 | 20 | | GA | | 0-6 | 23-71-11 | D00001 | P- | | | SM00001 | | WI | | 001-099 |
| 0044 | 20 | | GA | | 1-0 | 23-71-11 | D00001 | P- | | | SM00001 | | WI | | 115-199 |
| 0045 | 24 | | GK | | 44-0 | 23-22-11 | D00333 | 50 | | | D41541P | 17 | | | 001-099 |
| 0045 | 24 | | GK | | 46-0 | SPARE | D00333 | 50 | | | D41541P | 17 | | | 115-199 |
| 0046 | 22 | | GA | | 8-0 | 23-43-11 | D00333 | 33 | | | TB0113X | A002 | BJ | | 001-099 |
| 0046 | 22 | | GA | | 5-0 | 23-43-11 | D00333 | 33 | | | TB0113X | A002 | BJ | | 115-199 |
| 0047 | 20 | | GA | | 7-0 | 23-43-11 | D00333 | 37 | | | GD00605 | DC.. | 2 | | 001-099 |
| 0047 | 20 | | GA | | 5-0 | 23-43-11 | D00333 | 37 | | | GD00605 | DC.. | 2 | | 115-199 |
| 0048 | 22 | | GA | | 6-0 | 23-43-11 | D00333 | 44 | | | TB0116X | A015 | BJ | | 001-099 |
| 0048 | 22 | | GA | | 7-0 | 23-43-11 | D00333 | 44 | | | TB0116X | A015 | BJ | | 115-199 |
| 0049 | 22 | | GA | | 6-0 | 23-43-11 | D00333 | 39 | | | TB0116X | B015 | BJ | | 001-099 |
| 0049 | 22 | | GA | | 7-0 | 23-43-11 | D00333 | 39 | | | TB0116X | B015 | BJ | | 115-199 |
| 0050 | 22 | | GA | | 6-0 | 23-43-11 | D00333 | 38 | | | TB0116X | C015 | BJ | | 001-099 |
| 0050 | 22 | | GA | | 7-0 | 23-43-11 | D00333 | 38 | | | TB0116X | C015 | BJ | | 115-199 |
| 0051 | 20 | | GA | | 8-0 | 21-58-11 | D00333 | 45 | | | TB0113X | D002 | BJ | | 001-099 |
| 0051 | 20 | | GA | | 5-0 | 21-58-11 | D00333 | 45 | | | TB0113X | D002 | BJ | | 115-199 |
| 0052 | 20 | | GA | | 7-0 | 21-58-11 | D00333 | 42 | | | GD00606 | DC.. | 2 | | 001-099 |
| 0052 | 20 | | GA | | 5-0 | 21-58-11 | D00333 | 42 | | | GD00606 | DC.. | 2 | | 115-199 |
| 0053 | 24 | | GK | | 44-0 | 31-51-33 | D41541P | 41 | | | D00333 | 32 | | | 001-099 |
| 0053 | 24 | | GK | | 46-0 | 31-51-33 | D41541P | 41 | | | D00333 | 32 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2351 | 286N2351 | | | E4-3 SHELF TO P05 PILOTS OVERHEAD PANEL (continued) | | | | | | | | | | | | |
| 0054 | 22 | GA | | | 0-6 | 23-71-11 | D00001 | | F- | | SM00004 | | WI | | 115-199 | |
| 0055 | 24 | GK | | | 39-0 | SPARE | D00471 | | 12 | | D41541P | 51 | | | 001-099 | |
| 0055 | 22 | GA | | | 0-6 | 23-71-11 | D00001 | | G- | | SM00005 | | WI | | 115-199 | |
| 0060 | 24 | GK | | | 46-0 | 23-71-11 | D00001 | | H- | | D41541P | 44 | | | 001-099 | |
| 0061 | 22 | GA | | | 44-0 | 23-42-11 | D00333 | | 46 | | D41541P | 42 | | | 001-099 | |
| 1001 | 22 | GT | AC | | 44-0 | 23-42-11 | D41541P | | 34 | | D00333 | 21 | | | 001-099 | |
| 1001 | 22 | GT | AC | | 46-0 | 23-42-11 | D41541P | | 34 | | D00333 | 21 | | | 115-199 | |
| 1001Z | | | AC | | 0-0 | 23-42-11 | D41541P | | 35 | | D00333 | 24 | | | ALL | |
| 2501B | 24 | G2 | AA | | 39-0 | 23-41-11 | D00471 | | 8 | | D41541P | 23 | | | 001-099 | |
| 2501B | 24 | G2 | AA | | 38-0 | 23-41-11 | D00471 | | 8 | | D41541P | 23 | | | 115-199 | |
| 2501R | 24 | G2 | AA | | 0-0 | 23-41-11 | D00471 | | 7 | | D41541P | 24 | | | ALL | |
| 2501Z | | | AA | | 0-0 | 23-41-11 | D00471 | | DED | | D41541P | 25 | | | ALL | |
| 2502B | 24 | G2 | AB | | 46-0 | 23-71-11 | D00001 | | K | | D41541P | 29 | | | 001-099 | |
| 2502B | 24 | G2 | AB | | 49-0 | 23-71-11 | TB0115Y | C021 | BJ | | D41541P | 29 | | | 115-199 | |
| 2502R | 24 | G2 | AB | | 0-0 | 23-71-11 | D00001 | | L | | D41541P | 28 | | | 001-099 | |
| 2502R | 24 | G2 | AB | | 0-0 | 23-71-11 | TB0115Y | A021 | BJ | | D41541P | 28 | | | 115-199 | |
| 2502Z | | | AB | | 0-0 | 23-71-11 | D00001 | | DED | | D41541P | | | AA | 001-099 | |
| 2502Z | | | AB | | 0-0 | 23-71-11 | TB0115X | C020 | BJ | | D41541P | | | AA | 115-199 | |
| 2503B | 24 | G2 | AD | | 46-0 | 23-71-11 | D00001 | | V | | D41541P | 31 | | | 001-099 | |
| 2503B | 24 | G2 | AD | | 47-0 | 23-71-11 | D00001 | | V | | D41541P | 31 | | | 115-199 | |
| 2503R | 24 | G2 | AD | | 0-0 | 23-71-11 | D00001 | | W | | D41541P | 32 | | | ALL | |
| 2503Z | | | AD | | 0-0 | 23-71-11 | D00001 | | DED | | D41541P | | | AA | ALL | |
| 2504B | 24 | G2 | AE | | 46-0 | 23-71-11 | D00001 | | J- | | D41541P | 46 | | | 001-099 | |
| 2504B | 24 | G2 | AE | | 9-0 | 23-71-11 | D00001 | | K | | TB0115Y | C021 | BJ | | 115-199 | |
| 2504R | 24 | G2 | AE | | 0-0 | 23-71-11 | D00001 | | I- | | D41541P | 45 | | | 001-099 | |
| 2504R | 24 | G2 | AE | | 0-0 | 23-71-11 | D00001 | | L | | TB0115Y | A021 | BJ | | 115-199 | |
| 2504Z | | | AE | | 0-0 | 23-71-11 | D00001 | | DED | | D41541P | | | AA | 001-099 | |
| 2504Z | | | AE | | 0-0 | 23-71-11 | D00001 | | DED | | TB0115X | C020 | BJ | | 115-199 | |
| 2505B | 24 | G2 | AF | | 32-0 | 23-71-11 | TB0115Y | A021 | % | | SP00057 | 9 | | | 115-199 | |
| 2505R | 24 | G2 | AF | | 0-0 | 23-71-11 | TB0115Y | A022 | % | | SP00059 | 9 | | | 115-199 | |
| 2505Z | | | AF | | 0-0 | 23-71-11 | TB0115Y | C022 | % | | SP00061 | 9 | | | 115-199 | |
| 2506B | 24 | G2 | AG | | 32-0 | 23-71-11 | TB0115Y | A021 | % | | SP00067 | 9 | | | 115-199 | |
| 2506R | 24 | G2 | AG | | 0-0 | 23-71-11 | TB0115Y | A022 | % | | SP00065 | 9 | | | 115-199 | |
| 2506Z | | | AG | | 0-0 | 23-71-11 | TB0115Y | C022 | % | | SP00069 | 9 | | | 115-199 | |
| 2508B | 24 | G2 | AI | | 8-0 | 23-71-11 | TB0115Y | C022 | BJ | | SM00005 | | WI | | 115-199 | |
| 2508R | 24 | G2 | AI | | 0-0 | 23-71-11 | TB0115Y | A022 | BJ | | SM00004 | | WI | | 115-199 | |
| 2508Z | | | AI | | 0-0 | 23-71-11 | TB0115Y | C022 | BJ | | SM00REF | DED | | | 115-199 | |
| FRAA | | | | | 0-0 | 23-71-11 | D41541P | | | AA | D41541P | 40 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2352 | 286N2352 | | | | P11 TO E/E BAY - POWER DISTR-CAT L(B) | | | | | | | | | | | |
| 0002 | 24 | | GK | | 47-0 | SPARE | | D40614P | 49 | | | D40696P | 32 | | | 001-099 |
| 0003 | 24 | | GK | | 47-0 | SPARE | | D40614P | 50 | | | D40696P | 33 | | | 001-099 |
| 0004 | 24 | | GK | | 47-0 | SPARE | | D40614P | 4 | | | D40696P | 8 | | | ALL |
| 0006 | 22 | | GA | | 47-0 | 32-09-11 | | D40614P | 6 | | | D40696P | 7 | | | ALL |
| 0008 | 24 | | GK | | 47-0 | SPARE | | D40614P | 8 | | | D40696P | 9 | | | ALL |
| 0009 | 22 | | GA | | 49-0 | 76-11-21 | | D40614P | 9 | | | D40696P | 10 | | | 001-099 |
| 0009 | 22 | | GA | | 47-0 | 76-11-21 | | D40614P | 9 | | | D40696P | 10 | | | 115-199 |
| 0010 | 24 | | GK | | 40-0 | SPARE | | D40614P | 10 | | | D41880P | 10 | | | 115-199 |
| 0011 | 20 | | GA | | 47-0 | 21-58-11 | | D40614P | 11 | | | D40696P | 12 | | | ALL |
| 0012 | 24 | | GK | | 47-0 | 36-21-11 | | D40614P | 12 | | | D40696P | 13 | | | ALL |
| 0014 | 22 | | GA | | 40-0 | 21-44-11 | | D40614P | 14 | | | D41880P | 14 | | | ALL |
| 0015 | 22 | | GA | | 47-0 | 32-42-11 | | D40614P | 15 | | | D40696P | 17 | | | ALL |
| 0016 | 20 | | GA | | 47-0 | 21-51-12 | | D40614P | 16 | | | D40696P | 16 | | | ALL |
| 0018 | 22 | | GA | | 47-0 | 33-25-11 | | D40614P | 18 | | | D40696P | 20 | | | ALL |
| 0019 | 24 | | GK | | 47-0 | SPARE | | D40614P | 19 | | | D40696P | 21 | | | ALL |
| 0028 | 22 | | CQ | | 55-0 | 34-46-14 | | D40616P | 12 | | | SP02226 | | 9 | | 002 |
| 0029 | 20 | | GA | | 50-0 | 21-51-11 | | D40616P | 6 | | | D40810P | 7 | | | 001-099 |
| 0029 | 20 | | GA | | 49-0 | 21-51-11 | | D40614P | 29 | | | D40810P | 7 | | | 115-199 |
| 0034 | 18 | | GA | | 47-0 | 30-34-21 | | D40614P | 34 | 18 | | D40696P | 27 | 18 | | 001-099 |
| 0034 | 22 | | GA | | 47-0 | SPARE | | D40614P | 34 | | | D40696P | 27 | | | 115-199 |
| 0035 | 20 | | GA | | 47-0 | 27-62-11 | | D40616P | 4 | | | D40696P | 28 | | | ALL |
| 0039 | 24 | | GK | | 47-0 | 27-58-11 | | D40616P | 9 | | | D40696P | 35 | | | 001-099 |
| 0039 | 22 | | GA | | 47-0 | 27-58-11 | | D40616P | 9 | | | D40696P | 35 | | | 115-199 |
| 0040 | 24 | | GK | | 47-0 | 27-58-11 | | D40616P | 10 | | | D40696P | 36 | | | 001-099 |
| 0040 | 22 | | GA | | 47-0 | 27-58-11 | | D40616P | 10 | | | D40696P | 36 | | | 115-199 |
| 0044 | 24 | | GK | | 47-0 | 36-11-12 | | D40614P | 2 | | | D40696P | 1 | | | ALL |
| 0047 | 22 | | GA | | 47-0 | 27-51-51 | | D40614P | 38 | | | D40696P | 34 | | | ALL |
| 0070 | 22 | | GA | | 47-0 | 30-34-21 | | D40614P | 54 | | | D40696P | 30 | | | 115-199 |
| 0071 | 18 | | GA | | 47-0 | 30-34-21 | | D40614P | 55 | 18 | | D40696P | 50 | 18 | | 115-199 |
| 0101 | 20 | | GA | | 20-0 | 33-23-11 | | D41880P | 1 | | | D40696P | 41 | | | 001-099 |
| 0101 | 20 | | GA | | 21-0 | 33-23-11 | | D41880P | 1 | | | D40696P | 41 | | | 115-199 |
| 0102 | 20 | | GA | | 20-0 | 33-23-12 | | D41880P | 2 | | | D40696P | 42 | | | 001-099 |
| 0102 | 20 | | GA | | 21-0 | 33-23-12 | | D41880P | 2 | | | D40696P | 42 | | | 115-199 |
| 0103 | 20 | | GA | | 20-0 | 33-23-13 | | D41880P | 3 | | | D40696P | 43 | | | 001-099 |
| 0103 | 20 | | GA | | 21-0 | 33-23-13 | | D41880P | 3 | | | D40696P | 43 | | | 115-199 |
| 0104 | 20 | | GA | | 20-0 | 33-23-14 | | D41880P | 4 | | | D40696P | 44 | | | 001-099 |
| 0104 | 20 | | GA | | 21-0 | 33-23-14 | | D41880P | 4 | | | D40696P | 44 | | | 115-199 |
| 0105 | 22 | | GA | | 51-0 | 27-48-21 | | D40616P | 5 | | | D40810P | 5 | | | 001-099 |
| 0105 | 22 | | GA | | 49-0 | 27-48-21 | | D40616P | 5 | | | D40810P | 5 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2352 | 286N2352 | | | P11 TO E/E BAY - POWER DISTR-CAT L(B) (continued) | | | | | | | | | | | |
| 0110 | 22 | | GA | | 21-0 | 21-58-24 | D41880P | | 7 | | D40696P | | 14 | | 115-199 |
| 0111 | 22 | | GA | | 21-0 | 21-58-24 | D41880P | | 8 | | D40696P | | 15 | | 115-199 |
| 0112 | 22 | | GA | | 21-0 | 21-58-24 | D41880P | | 9 | | D40696P | | 19 | | 115-199 |
| 0113 | 18 | | GA | | 21-0 | 21-58-21 | D41754P | | 3 | | D40696P | | 3 | 18 | ALL |
| 0114 | 18 | | GA | | 21-0 | 21-58-21 | D41754P | | 4 | | D40696P | | 22 | 18 | ALL |
| 0115 | 18 | | GA | | 21-0 | 21-58-21 | D41754P | | 5 | | D40696P | | 11 | 18 | ALL |
| 0128 | 20 | | GA | | 47-0 | 36-11-11 | D40614P | | 43 | | D40696P | | 38 | | ALL |
| 0201 | 20 | | GA | | 50-0 | 21-51-23 | D40616P | | 8 | | D40810P | | 1 | | 001-099 |
| 0201 | 20 | | GA | | 49-0 | SPARE | D40614P | | 1 | | D40810P | | 1 | | 115-199 |
| 0206 | 20 | | GA | | 47-0 | 74-31-11 | D40614P | | 46 | | D40696P | | 46 | | ALL |
| 0501 | 24 | | GK | | 47-0 | SPARE | D40614P | | 3 | | D40696P | | 2 | | ALL |
| 0502 | 20 | | GA | | 20-0 | 21-45-11 | D41880P | | 5 | | D40696P | | 5 | | 001-099 |
| 0502 | 20 | | GA | | 21-0 | 21-45-11 | D41880P | | 5 | | D40696P | | 5 | | 115-199 |
| 0503 | 20 | | GA | | 20-0 | 21-45-11 | D41880P | | 6 | | D40696P | | 6 | | 001-099 |
| 0503 | 20 | | GA | | 21-0 | 21-45-11 | D41880P | | 6 | | D40696P | | 6 | | 115-199 |
| 0504 | 20 | | GA | | 15-0 | 30-41-11 | D41914P | | 3 | | D41754P | | 8 | | 001-099 |
| 0504 | 20 | | GA | | 16-0 | 30-41-11 | D41914P | | 3 | | D41754P | | 8 | | 115-199 |
| 0505 | 20 | | GA | | 15-0 | 30-41-11 | D41914P | | 4 | | D41754P | | 7 | | 001-099 |
| 0505 | 20 | | GA | | 16-0 | 30-41-11 | D41914P | | 4 | | D41754P | | 7 | | 115-199 |
| 0507 | 22 | | GA | | 50-0 | 26-18-11 | D40614P | | 28 | | D40810P | | 4 | | 001-099 |
| 0507 | 22 | | GA | | 49-0 | 26-18-11 | D40614P | | 28 | | D40810P | | 4 | | 115-199 |
| 0602 | 22 | | GA | | 50-0 | 27-23-21 | D40614P | | 13 | | D40810P | | 2 | | 001-099 |
| 0602 | 22 | | GA | | 49-0 | 27-23-21 | D40614P | | 13 | | D40810P | | 2 | | 115-199 |
| 0603 | 24 | | GK | | 50-0 | SPARE | D40614P | | 17 | | D40810P | | 3 | | 001-099 |
| 0603 | 24 | | GK | | 49-0 | SPARE | D40614P | | 17 | | D40810P | | 3 | | 115-199 |
| 0604 | 24 | | GK | | 50-0 | SPARE | D40614P | | 20 | | D40810P | | 6 | | 001-099 |
| 0604 | 24 | | GK | | 49-0 | SPARE | D40614P | | 20 | | D40810P | | 6 | | 115-199 |
| 0605 | 24 | | GK | | 50-0 | SPARE | D40614P | | 21 | | D40810P | | 8 | | 001-099 |
| 0605 | 24 | | GK | | 49-0 | SPARE | D40614P | | 21 | | D40810P | | 8 | | 115-199 |
| 0606 | 24 | | GK | | 49-0 | SPARE | D40614P | | 22 | | D40810P | | 9 | | 115-199 |
| 0607 | 24 | | GK | | 49-0 | SPARE | D40614P | | 23 | | D40810P | | 10 | | 115-199 |
| 0608 | 22 | | GA | | 50-0 | 27-23-21 | D40614P | | 24 | | D40810P | | 11 | | 001-099 |
| 0608 | 20 | | GA | | 49-0 | 27-23-21 | D40614P | | 24 | | D40810P | | 11 | | 115-199 |
| 0609 | 20 | | GA | | 50-0 | SPARE | D40614P | | 25 | | D40810P | | 12 | | 001-099 |
| 0609 | 20 | | GA | | 49-0 | SPARE | D40614P | | 25 | | D40810P | | 12 | | 115-199 |
| 0614 | 22 | | GA | | 40-0 | SPARE | D40614P | | 26 | | D41880P | | 18 | | 115-199 |
| 0615 | 22 | | GA | | 40-0 | SPARE | D40614P | | 27 | | D41880P | | 19 | | 115-199 |
| 0616 | 22 | | GA | | 40-0 | SPARE | D40614P | | 30 | | D41880P | | 20 | | 115-199 |
| 0619 | 24 | | GK | | 47-0 | SPARE | D40614P | | 33 | | D40696P | | 4 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|--|
| Wire No. | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2352 | 286N2352 | | | | P11 TO E/E BAY - POWER DISTR-CAT L(B) (continued) | | | | | | | | | | | |
| 0620 | 24 | | GK | | 47-0 | SPARE | D40614P | | 35 | | D40696P | 23 | | | 115-199 | |
| 0621 | 24 | | GK | | 47-0 | SPARE | D40614P | | 36 | | D40696P | 24 | | | 115-199 | |
| 0622 | 24 | | GK | | 47-0 | 21-61-51 | D40614P | | 37 | | D40696P | 25 | | | ALL | |
| 0623 | 22 | | GA | | 47-0 | 32-42-11 | D40614P | | 39 | | D40696P | 26 | | | 115-199 | |
| 0625 | 22 | | GA | | 47-0 | 30-34-21 | D40614P | | 41 | | D40696P | 30 | | | 001-099 | |
| 0626 | 22 | | GA | | 47-0 | SPARE | D40616P | | 1 | | D40696P | 31 | | | 115-199 | |
| 0627 | 20 | | GA | | 47-0 | SPARE | D40616P | | 2 | | D40696P | 32 | | | 115-199 | |
| 0628 | 20 | | GA | | 47-0 | SPARE | D40616P | | 3 | | D40696P | 33 | | | 115-199 | |
| 0629 | 20 | | GA | | 47-0 | SPARE | D40616P | | 6 | | D40696P | 37 | | | 115-199 | |
| 0630 | 20 | | GA | | 47-0 | SPARE | D40616P | | 7 | | D40696P | 39 | | | 115-199 | |
| 0631 | 20 | | GA | | 47-0 | SPARE | D40616P | | 8 | | D40696P | 40 | | | 115-199 | |
| 0632 | 20 | | GA | | 47-0 | SPARE | D40616P | | 11 | | D40696P | 45 | | | 115-199 | |
| 0633 | 20 | | GA | | 47-0 | SPARE | D40616P | | 12 | | D40696P | 47 | | | 001, 003-099, 115-199 | |
| 0633 | 20 | | GA | | 47-0 | SPARE | D40616P | REF | JB | | D40696P | 47 | | | 002 | |
| 0636 | 20 | | GA | | 15-0 | SPARE | D41914P | | 5 | | D41880P | 27 | | | 115-199 | |
| 0637 | 20 | | GA | | 15-0 | SPARE | D41914P | | 6 | | D41880P | 22 | | | 115-199 | |
| 0638 | 20 | | GA | | 15-0 | SPARE | D41914P | | 7 | | D41880P | 28 | | | 115-199 | |
| 0639 | 20 | | GA | | 15-0 | SPARE | D41914P | | 8 | | D41880P | 24 | | | 115-199 | |
| 0640 | 20 | | GA | | 15-0 | SPARE | D41914P | | 9 | | D41880P | 25 | | | 115-199 | |
| 0641 | 20 | | GA | | 15-0 | SPARE | D41914P | | 10 | | D41880P | 26 | | | 115-199 | |
| 0643 | 12 | | GA | | 15-0 | SPARE | D41914P | | 18 | | D41754P | 11 | | | 115-199 | |
| 0647 | 20 | | GA | | 40-0 | SPARE | D40614P | | 44 | | D41880P | 33 | | | 115-199 | |
| 0648 | 20 | | GA | | 40-0 | SPARE | D40614P | | 45 | | D41880P | 34 | | | 115-199 | |
| 0649 | 20 | | GA | | 21-0 | SPARE | D40696P | | 52 | | D41880P | 31 | | | 115-199 | |
| 0650 | 20 | | GA | | 21-0 | SPARE | D40696P | | 53 | | D41880P | 32 | | | 115-199 | |
| 0651 | 20 | | GA | | 15-0 | SPARE | D41880P | | 29 | | D41914P | 19 | | | 115-199 | |
| 0652 | 20 | | GA | | 15-0 | SPARE | D41880P | | 30 | | D41914P | 20 | | | 115-199 | |
| 2001B | 12 | | GB | AA | 15-0 | 30-41-11 | D41754P | | 1 | | D41914P | 14 | | | 001-099 | |
| 2001B | 12 | | GB | AA | 16-0 | 30-41-11 | D41754P | | 1 | | D41914P | 14 | | | 115-199 | |
| 2001R | 12 | | GB | AA | 0-0 | 30-41-11 | D41754P | | 2 | | D41914P | 16 | | | ALL | |
| W2353 | 286N2353 | | | | P61 PANEL-REMOTE PANEL TO E/E- CHANNEL L | | | | | | | | | | | |
| 0001 | 22 | | GA | | 43-0 | 22-41-13 | D41101J | | 4 | | D41741P | 4 | | | 001-099 | |
| 0001 | 22 | | GA | | 41-0 | 22-41-13 | D41101J | | 4 | | D41741P | 4 | | | 115-199 | |
| 0002 | 22 | | GA | | 43-0 | 22-41-13 | D41101J | | 5 | | D41741P | 5 | | | 001-099 | |
| 0002 | 22 | | GA | | 41-0 | 22-41-13 | D41101J | | 5 | | D41741P | 5 | | | 115-199 | |
| 0003 | 22 | | GA | | 43-0 | 22-41-13 | D41101J | | 6 | | D41741P | 6 | | | 001-099 | |
| 0003 | 22 | | GA | | 41-0 | 22-41-13 | D41101J | | 6 | | D41741P | 6 | | | 115-199 | |
| 0004 | 22 | | GA | | 43-0 | 22-41-13 | D41101J | | 7 | | D41741P | 7 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 10

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2353 | 286N2353 | | | P61 PANEL-REMOTE PANEL TO E/E- CHANNEL L (continued) | | | | | | | | | | | |
| 0004 | 22 | | GA | | 41-0 | 22-41-13 | D41101J | | 7 | | D41741P | | 7 | | 115-199 |
| 0005 | 22 | | GA | | 43-0 | 22-41-13 | D41101J | | 8 | | D41741P | | 8 | | 001-099 |
| 0005 | 22 | | GA | | 41-0 | 22-41-13 | D41101J | | 8 | | D41741P | | 8 | | 115-199 |
| 0006 | 22 | | GA | | 43-0 | 22-41-13 | D41101J | | 9 | | D41741P | | 9 | | 001-099 |
| 0006 | 22 | | GA | | 41-0 | 22-41-13 | D41101J | | 9 | | D41741P | | 9 | | 115-199 |
| 0007 | 22 | | GA | | 43-0 | 22-41-13 | D41101J | | 10 | | D41741P | | 10 | | 001-099 |
| 0007 | 22 | | GA | | 41-0 | 22-41-13 | D41101J | | 10 | | D41741P | | 10 | | 115-199 |
| 0008 | 22 | | GA | | 43-0 | SPARE | D41101J | | 11 | | D41741P | | 11 | | 001-099 |
| 0008 | 22 | | GA | | 41-0 | SPARE | D41101J | | 11 | | D41741P | | 11 | | 115-199 |
| 0009 | 22 | | GA | | 43-0 | SPARE | D41101J | | 12 | | D41741P | | 12 | | 001-099 |
| 0009 | 22 | | GA | | 41-0 | SPARE | D41101J | | 12 | | D41741P | | 12 | | 115-199 |
| 0010 | 22 | | GA | | 43-0 | SPARE | D41101J | | 13 | | D41741P | | 13 | | 001-099 |
| 0010 | 22 | | GA | | 41-0 | SPARE | D41101J | | 13 | | D41741P | | 13 | | 115-199 |
| 0011 | 22 | | GA | | 43-0 | 22-41-13 | D41101J | | 14 | | D41741P | | 14 | | 001-099 |
| 0011 | 22 | | GA | | 41-0 | 22-41-13 | D41101J | | 14 | | D41741P | | 14 | | 115-199 |
| 5001B | 24 | | G2 | AA | 43-0 | 22-41-13 | D41101J | | 2 | | D41741P | | 2 | | 001-099 |
| 5001B | 24 | | G2 | AA | 41-0 | 22-41-13 | D41101J | | 2 | | D41741P | | 2 | | 115-199 |
| 5001R | 24 | | G2 | AA | 0-0 | 22-41-13 | D41101J | | 1 | | D41741P | | 1 | | ALL |
| 5001Z | | | | AA | 0-0 | 22-41-13 | D41101J | | 3 | | D41741P | | 3 | | ALL |
| W2354 | 286N2354 | | | P11 TO E/E BAY - POWER DISTR CAT R(A) | | | | | | | | | | | |
| 0001 | 20 | | GA | | 32-0 | 22-11-21 | D40618P | | 3 | | D41328P | | 3 | | 001-099 |
| 0001 | 20 | | GA | | 33-0 | 22-11-21 | D40618P | | 3 | | D41328P | | 3 | | 115-199 |
| 0002 | 22 | | GA | | 32-0 | 34-31-21 | D40618P | | 4 | | D41328P | | 2 | | 001-099 |
| 0002 | 22 | | GA | | 33-0 | 34-31-21 | D40618P | | 4 | | D41328P | | 2 | | 115-199 |
| 0003 | 22 | | GA | | 32-0 | 34-61-21 | D40618P | | 5 | | D41328P | | 5 | | 001-099 |
| 0003 | 22 | | GA | | 33-0 | 34-61-21 | D40618P | | 5 | | D41328P | | 5 | | 115-199 |
| 0004 | 24 | | GK | | 32-0 | 34-22-26 | D40618P | | 6 | | D41328P | | 14 | | 001, 003-099 |
| 0004 | 24 | | GK | | 32-0 | SPARE | D40618P | | 6 | | D41328P | | 14 | | 002 |
| 0004 | 24 | | GK | | 33-0 | 34-22-26 | D40618P | | 6 | | D41328P | | 14 | | 115-199 |
| 0005 | 20 | | GA | | 32-0 | 22-11-22 | D40618P | | 7 | | D41328P | | 11 | | 001-099 |
| 0005 | 20 | | GA | | 33-0 | 22-11-22 | D40618P | | 7 | | D41328P | | 11 | | 115-199 |
| 0006 | 20 | | GA | | 32-0 | 22-11-22 | D40618P | | 15 | | D41328P | | 6 | | 001-099 |
| 0006 | 20 | | GA | | 33-0 | 22-11-22 | D40618P | | 15 | | D41328P | | 6 | | 115-199 |
| 0007 | 24 | | GK | | 32-0 | 34-22-26 | D40618P | | 23 | | D41328P | | 13 | | 001-099 |
| 0007 | 24 | | GK | | 33-0 | 34-22-26 | D40618P | | 23 | | D41328P | | 13 | | 115-199 |
| 0008 | 24 | | GK | | 32-0 | 34-12-21 | D40618P | | 25 | | D41328P | | 8 | | 001-099 |
| 0008 | 24 | | GK | | 33-0 | 34-12-21 | D40618P | | 25 | | D41328P | | 8 | | 115-199 |
| 0009 | 24 | | GK | | 32-0 | 34-12-21 | D40618P | | 26 | | D41328P | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 11

Dec 18/2007



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2354 | 286N2354 | | | | P11 TO E/E BAY - POWER DISTR CAT R(A) (continued) | | | | | | | | | | | |
| 0009 | 24 | | GK | | 33-0 | 34-12-21 | | D40618P | 26 | | | D41328P | 9 | | | 115-199 |
| 0010 | 24 | | GK | | 32-0 | 34-12-21 | | D40618P | 27 | | | D41328P | 1 | | | 001-099 |
| 0010 | 24 | | GK | | 33-0 | 34-12-21 | | D40618P | 27 | | | D41328P | 1 | | | 115-199 |
| 0011 | 22 | | GA | | 42-0 | 32-09-11 | | D40824P | 15 | | | D40702P | 8 | | | 001-099 |
| 0011 | 22 | | GA | | 42-0 | 32-01-11 | | D40824P | 15 | | | D40702P | 8 | | | 115-199 |
| 0012 | 24 | | GK | | 32-0 | 34-12-21 | | D40618P | 33 | | | D41328P | 12 | | | 001-099 |
| 0012 | 24 | | GK | | 33-0 | 34-12-21 | | D40618P | 33 | | | D41328P | 12 | | | 115-199 |
| 0013 | 22 | | GA | | 38-0 | 77-31-11 | | D40824P | 21 | | | D40704P | 9 | | | 001-099 |
| 0013 | 22 | | GA | | 37-0 | 77-31-11 | | D40824P | 21 | | | D40704P | 9 | | | 115-199 |
| 0014 | 22 | | GA | | 42-0 | 32-61-11 | | D40824P | 8 | | | SP01952 | 9 | | | 001-002, 115-199 |
| 0014 | 22 | | GA | | 38-0 | 32-61-11 | | D40824P | 8 | | | SP01952 | 9 | | | 003-099 |
| 0015 | 22 | | GA | | 42-0 | SPARE | | D40824P | 14 | | | D40702P | 14 | | | ALL |
| 0016 | 22 | | GA | | 42-0 | 29-33-11 | | D40824P | 19 | | | D40702P | 10 | | | 001-099 |
| 0016 | 22 | | GA | | 164-0 | 29-33-11 | | D40824P | 19 | | | D42214P | 6 | | | 115-199 |
| 0017 | 22 | | GA | | 42-0 | 25-66-11 | | D40702P | 7 | | | D40824P | 7 | | | ALL |
| 0019 | 18 | | GA | | 40-0 | SPARE | | D40710P | 9 | | | D40618P | 17 | 18 | | 115-199 |
| 0020 | 22 | | GA | | 42-0 | 34-53-21 | | D40618P | 54 | | | SP27001 | 9 | | | 001-099 |
| 0020 | 22 | | GA | | 39-0 | 34-53-21 | | SP27001 | | 9 | | D40618P | 54 | | | 115-199 |
| 0021 | 22 | | GA | | 38-0 | 27-38-11 | | D40824P | 11 | | | D40704P | 1 | | | 001-099 |
| 0021 | 22 | | GA | | 37-0 | 27-38-11 | | D40824P | 11 | | | D40704P | 1 | | | 115-199 |
| 0022 | 24 | | GK | | 38-0 | 79-32-11 | | D40824P | 22 | | | D40704P | 2 | | | 001-099 |
| 0022 | 24 | | GK | | 37-0 | 79-32-11 | | D40824P | 22 | | | D40704P | 2 | | | 115-199 |
| 0023 | 22 | | GA | | 38-0 | 31-41-21 | | D40824P | 13 | | | D40704P | 3 | | | 001-099 |
| 0023 | 22 | | GA | | 37-0 | 31-41-21 | | D40824P | 13 | | | D40704P | 3 | | | 115-199 |
| 0024 | 22 | | GA | | 38-0 | 31-41-21 | | D40824P | 12 | | | D40704P | 4 | | | 001-099 |
| 0024 | 22 | | GA | | 37-0 | 31-41-21 | | D40824P | 12 | | | D40704P | 4 | | | 115-199 |
| 0025 | 22 | | GA | | 38-0 | 35-11-13 | | D40704P | 5 | | | D40824P | 24 | | | 001-099 |
| 0025 | 22 | | GA | | 37-0 | SPARE | | D40704P | 5 | | | D40824P | 24 | | | 115-199 |
| 0026 | 20 | | GA | | 39-0 | 23-71-11 | | D40618P | 28 | | | D40672P | 1 | | | ALL |
| 0028 | 20 | | GA | | 33-0 | 34-21-21 | | D40618P | 8 | | | D41916P | 5 | | | 001-099 |
| 0028 | 20 | | GA | | 34-0 | 34-21-21 | | D40618P | 8 | | | D41916P | 8 | | | 115-199 |
| 0029 | 24 | | GK | | 40-0 | 27-81-11 | | D40618P | 29 | | | D40710P | 3 | | | 001-099 |
| 0029 | 22 | | GA | | 40-0 | 27-81-11 | | D40618P | 29 | | | D40710P | 3 | | | 115-199 |
| 0030 | 24 | | GK | | 40-0 | 27-81-11 | | D40618P | 30 | | | D40710P | 5 | | | 001-099 |
| 0030 | 22 | | GA | | 40-0 | 27-81-11 | | D40618P | 30 | | | D40710P | 5 | | | 115-199 |
| 0031 | 24 | | GK | | 40-0 | 27-81-11 | | D40618P | 31 | | | D40710P | 4 | | | 001-099 |
| 0031 | 22 | | GA | | 40-0 | 27-81-11 | | D40618P | 31 | | | D40710P | 4 | | | 115-199 |
| 0034 | 22 | | GA | | 38-0 | 27-18-11 | | D40824P | 10 | | | D40704P | 10 | | | 001-099 |
| 0034 | 22 | | GA | | 37-0 | 27-18-11 | | D40824P | 10 | | | D40704P | 10 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 12

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2354 | 286N2354 | | | P11 TO E/E BAY - POWER DISTR CAT R(A) (continued) | | | | | | | | | | | |
| 0040 | 22 | | GA | | 39-0 | SPARE | D40618P | 12 | | | D40672P | 7 | | | 115-199 |
| 0042 | 22 | | GA | | 24-0 | 32-61-11 | D40702P | 1 | | | SP01950 | | 9 | | 001-099 |
| 0042 | 22 | | GA | | 42-0 | 32-61-11 | D40702P | 1 | | | SP01950 | | 9 | | 115-199 |
| 0043 | 22 | | GA | | 40-0 | 34-33-21 | D40618P | 1 | | | D40710P | 1 | | | ALL |
| 0045 | 22 | | GA | | 40-0 | 24-41-11 | D40824P | 18 | | | D40710P | 2 | | | ALL |
| 0049Y | 22 | | QB | | 37-0 | 27-41-21 | D40618P | 9 | | | D41918P | 9 | | | ALL |
| 0050 | 20 | | GA | | 43-0 | 23-11-21 | D40618P | 10 | | | D40700P | 5 | | | 001-099 |
| 0050 | 20 | | GA | | 165-0 | 23-11-21 | D40618P | 10 | | | D41830P | 1 | | | 115-199 |
| 0051 | 20 | | GA | | 43-0 | 23-11-21 | D40618P | 11 | | | D40700P | 6 | | | 001-099 |
| 0051 | 20 | | GA | | 165-0 | 23-11-21 | D40618P | 11 | | | D41830P | 2 | | | 115-199 |
| 0052 | 20 | | GA | | 43-0 | 23-11-21 | D40618P | 13 | | | D40700P | 7 | | | 001-099 |
| 0052 | 20 | | GA | | 165-0 | 23-11-21 | D40618P | 13 | | | D41830P | 3 | | | 115-199 |
| 0054 | 16 | | GA | | 39-0 | 23-12-21 | D40618P | 34 | 16 | | D40672P | 4 | | | ALL |
| 0058 | 22 | | GA | | 39-0 | 23-31-17 | D40618P | 2 | | | D40672P | 6 | | | 001-099 |
| 0058 | 22 | | GA | | 39-0 | SPARE | D40618P | 2 | | | D40672P | 6 | | | 115-199 |
| 0061 | 20 | | GA | | 165-0 | 21-51-13 | D40824P | 4 | | | D42212P | 7 | | | 115-199 |
| 0062 | 20 | | GA | | 165-0 | SPARE | D40824P | 5 | | | D42212P | 8 | | | 115-199 |
| 0065 | 22 | | GA | | 42-0 | 52-71-11 | D40824P | 25 | | | D40702P | 15 | | | ALL |
| 0066 | 22 | | GA | | 7-0 | 29-32-31 | D40704P | 6 | | | SP00556 | | 9 | | ALL |
| 0086 | 22 | | GA | | 43-0 | 34-55-21 | D40618P | 16 | | | D40700P | 4 | | | 001-099 |
| 0115 | 22 | | GA | | 37-0 | 27-48-11 | D40618P | 35 | | | D41918P | 15 | | | ALL |
| 0137 | 22 | | GA | | 41-0 | 34-51-21 | D40618P | 37 | | | D43015P | 5 | | | 001-099 |
| 0137 | 22 | | GA | | 164-0 | 34-51-21 | D40618P | 37 | | | D41908P | 5 | | | 115-199 |
| 0151 | 22 | | GA | | 37-0 | 27-09-11 | D40618P | 51 | | | D41918P | 1 | | | ALL |
| 0152 | 22 | | GA | | 37-0 | 27-09-11 | D40618P | 52 | | | D41918P | 2 | | | ALL |
| 0217 | 22 | | GA | | 36-0 | 27-32-21 | D40824P | 17 | | | D41918P | 7 | | | 001-099 |
| 0217 | 22 | | GA | | 37-0 | 27-32-21 | D40824P | 17 | | | D41918P | 7 | | | 115-199 |
| 0301 | 22 | | GA | | 36-0 | 23-51-11 | D40672P | 9 | | | TB0121X | D005 | BJ | | 001-099 |
| 0301 | 22 | | GA | | 39-0 | 23-51-11 | D40672P | 9 | | | TB0121Z | 11 | BJ | | 115-199 |
| 0361 | 22 | | GA | | 42-0 | 29-33-11 | D40824P | 35 | | | D40702P | 12 | | | 001-099 |
| 0361 | 22 | | GA | | 164-0 | 29-33-11 | D40824P | 35 | | | D42214P | 7 | | | 115-199 |
| 0362 | 22 | | GA | | 42-0 | 29-33-11 | D40824P | 36 | | | D40702P | 11 | | | 001-099 |
| 0362 | 22 | | GA | | 164-0 | 29-33-11 | D40824P | 36 | | | D42214P | 8 | | | 115-199 |
| 0514 | 22 | | GA | | 165-0 | SPARE | D40824P | 6 | | | D42212P | 9 | | | 115-199 |
| 0515 | 16 | | GA | | 163-0 | SPARE | D40824P | 43 | | | D41908P | 4 | | | 115-199 |
| 0597 | 22 | | GA | | 42-0 | SPARE | D40618P | 18 | | | D40702P | 2 | | | 115-199 |
| 0598 | 22 | | GA | | 42-0 | SPARE | D40618P | 20 | | | D40702P | 3 | | | 115-199 |
| 0601 | 22 | | GA | | 37-0 | SPARE | D40824P | 20 | | | D40704P | 11 | | | 115-199 |
| 0602 | 22 | | GA | | 37-0 | SPARE | D40618P | 36 | | | D40704P | 12 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 13

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2354 | 286N2354 | | | | P11 TO E/E BAY - POWER DISTR CAT R(A) (continued) | | | | | | | | | | | | |
| 0603 | 22 | | GA | | 37-0 | SPARE | | D40618P | | 38 | | D41918P | | 5 | | 115-199 | |
| 0604 | 22 | | GA | | 37-0 | SPARE | | D40618P | | 40 | | D41918P | | 6 | | 115-199 | |
| 0605 | 22 | | GA | | 37-0 | SPARE | | D40618P | | 41 | | D41918P | | 8 | | 115-199 | |
| 0608 | 22 | | GA | | 42-0 | SPARE | | D40618P | | 47 | | D40702P | | 5 | | 115-199 | |
| 0610 | 22 | | GA | | 42-0 | SPARE | | D40618P | | 49 | | D40702P | | 6 | | 115-199 | |
| 0624 | 18 | | GA | | 40-0 | SPARE | | D40824P | | 41 | | D40710P | | 7 | | 115-199 | |
| 0630 | 18 | | GA | | 163-0 | SPARE | | D40824P | | 38 | | D41908P | | 10 | | 115-199 | |
| 0640 | 18 | | GA | | 39-0 | SPARE | | D40824P | | 34 | | D40672P | | 10 | | 115-199 | |
| 0641 | 22 | | GA | | 33-0 | 34-61-25 | | D40618P | | 53 | | D41328P | | 7 | | 115-199 | |
| 0642 | 22 | | GA | | 164-0 | SPARE | | D42214P | | 4 | | D40618P | | 44 | | 115-199 | |
| 0643 | 22 | | GA | | 164-0 | SPARE | | D42214P | | 2 | | D40824P | | 2 | | 115-199 | |
| 0644 | 22 | | GA | | 165-0 | SPARE | | D42212P | | 5 | | D40618P | | 45 | | 115-199 | |
| 0645 | 22 | | GA | | 165-0 | SPARE | | D42212P | | 3 | | D40824P | | 3 | | 115-199 | |
| W2355 | 286N2355 | | | | CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL L | | | | | | | | | | | | |
| 0001 | 22 | | GA | | 36-0 | 22-11-12 | | TB0065X | A001 | BJ | | D41701P | | 1 | | ALL | |
| 0002 | 22 | | GA | | 36-0 | 22-11-12 | | TB0065X | B001 | BJ | | D41701P | | 2 | | ALL | |
| 0003 | 22 | | GA | | 36-0 | 22-11-12 | | TB0065X | C001 | BJ | | D41701P | | 3 | | ALL | |
| 0004 | 22 | | GA | | 2-0 | 22-11-12 | | TB0065X | D001 | BJ | | TB0065X | D002 | BJ | | ALL | |
| 0005 | 22 | | GA | | 36-0 | 22-11-12 | | TB0065X | A002 | BJ | | D41701P | | 4 | | ALL | |
| 0006 | 22 | | GA | | 36-0 | 22-11-12 | | TB0065X | B002 | BJ | | D41701P | | 5 | | ALL | |
| 0007 | 22 | | GA | | 36-0 | 22-11-12 | | TB0065X | C002 | BJ | | D41701P | | 6 | | ALL | |
| 0008 | 22 | | GA | | 36-0 | 22-12-11 | | D40501P | | 1 | | D41701P | | 7 | | ALL | |
| 0009 | 22 | | GA | | 36-0 | 22-12-11 | | D40501P | | 2 | | D41701P | | 8 | | ALL | |
| 0010 | 24 | | GK | | 36-0 | 22-32-15 | | D40501P | | 3 | | D41711P | | 1 | | ALL | |
| 0011 | 24 | | GK | | 36-0 | 22-32-15 | | D40501P | | 4 | | D41711P | | 2 | | ALL | |
| 0012 | 24 | | GK | | 33-0 | 22-32-15 | | D04452 | | 8 | | D41711P | | 5 | | ALL | |
| 0013 | 24 | | GK | | 33-0 | 22-32-15 | | D04452 | | 9 | | D41711P | | 3 | | ALL | |
| 0014 | 24 | | GK | | 36-0 | 22-32-15 | | D40501P | | 8 | | D41711P | | 6 | | ALL | |
| 0015 | 24 | | GK | | 33-0 | 22-32-15 | | D04452 | | 10 | | D41711P | | 4 | | 001-099 | |
| 0015 | 24 | | GK | | 35-0 | 22-32-15 | | D04452 | | 10 | | D41711P | | 25 | | 115-199 | |
| 0016 | 24 | | GK | | 32-0 | 22-31-11 | | D00399 | | X | | D41711P | | 7 | | ALL | |
| 0017 | 20 | | GA | | 32-0 | 22-31-11 | | D00399 | | Y | | D41711P | | 8 | | ALL | |
| 0018 | 20 | | GA | | 6-0 | 22-31-11 | | D00399 | | Z | | GD02316 | AC.. | 2 | | ALL | |
| 0019 | 20 | | GA | | 6-0 | 22-31-11 | | D00399 | | A- | | GD02316 | ST.. | 2 | | ALL | |
| 0020 | 20 | | GA | | 6-0 | 22-31-11 | | D00399 | | B- | | GD02316 | AC.. | 2 | | 001-099 | |
| 0020 | 20 | | GA | | 8-0 | 22-31-11 | | D00399 | | B- | | GD02316 | AC.. | 2 | | 115-199 | |
| 0023 | 22 | | GA | | 0-10 | 22-32-13 | | D00399 | | C | | SM00001 | | 9 | | ALL | |
| 0024 | 22 | | GA | | 0-10 | 22-32-13 | | D00399 | | B | | SM00001 | | 9 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 14

Dec 18/2007



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|--------|---------|------|-------------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W2355 | 286N2355 | | | CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL L (continued) | | | | | | | | | | | | |
| 0027 | 22 | GA | | | 41-0 | 27-48-11 | D02542 | 8 | | | | D41709P | 16 | | | 001-099 |
| 0027 | 22 | GA | | | 43-0 | 27-48-11 | D02542 | 8 | | | | D41709P | 16 | | | 115-199 |
| 0028 | 22 | GA | | | 41-0 | 27-48-11 | D02542 | 6 | | | | D41709P | 17 | | | 001-099 |
| 0028 | 22 | GA | | | 40-0 | 27-48-11 | D02542 | 6 | | | | D41709P | 17 | | | 115-199 |
| 0029 | 22 | GA | | | 41-0 | 27-48-11 | D02542 | 7 | | | | D41709P | 18 | | | 001-099 |
| 0029 | 22 | GA | | | 40-0 | 27-48-11 | D02542 | 7 | | | | D41709P | 18 | | | 115-199 |
| 0030 | 24 | GK | | | 40-0 | 31-51-42 | D04452 | 6 | | | | D41709P | 6 | | | 001-099 |
| 0030 | 24 | GK | | | 39-0 | 31-51-42 | D04452 | 6 | | | | D41709P | 6 | | | 115-199 |
| 0031 | 20 | GA | | | 2-0 | 31-51-42 | D04452 | 7 | | | | GD02749 | DC.. | 2 | | ALL |
| 0032 | 22 | GA | | | 40-0 | 27-32-11 | SP00173 | | 9 | | | D41709P | 13 | | | ALL |
| 0033 | 22 | GA | | | 40-0 | 27-32-11 | SP00175 | | 9 | | | D41709P | 14 | | | ALL |
| 0038 | 20 | GA | | | 48-0 | 27-62-11 | D40501P | 14 | | | | D41713P | 4 | | | 001-099 |
| 0038 | 20 | GA | | | 47-0 | 27-62-11 | D40501P | 14 | | | | D41713P | 4 | | | 115-199 |
| 0039 | 20 | GA | | | 48-0 | 27-62-11 | D40501P | 15 | | | | D41713P | 5 | | | 001-099 |
| 0039 | 20 | GA | | | 47-0 | 27-62-11 | D40501P | 15 | | | | D41713P | 5 | | | 115-199 |
| 0040 | 20 | GA | | | 48-0 | 27-62-11 | D40501P | 21 | | | | D41713P | 6 | | | 001-099 |
| 0040 | 20 | GA | | | 47-0 | 27-62-11 | D40501P | 21 | | | | D41713P | 6 | | | 115-199 |
| 0041 | 20 | GA | | | 48-0 | 27-62-11 | D40501P | 23 | | | | D41713P | 7 | | | 001-099 |
| 0041 | 20 | GA | | | 47-0 | 27-62-11 | D40501P | 23 | | | | D41713P | 7 | | | 115-199 |
| 0042 | 24 | GK | | | 45-0 | 21-31-11 | D04452 | 17 | | | | D41713P | 9 | | | 001-099 |
| 0042 | 24 | GK | | | 48-0 | 21-31-11 | D04452 | 17 | | | | D41713P | 9 | | | 115-199 |
| 0043Y | 20 | QB | | | 41-0 | 27-41-31 | D41709P | 5 | | | | SP00397 | | 9 | | ALL |
| 0044 | 24 | GK | | | 35-0 | 73-21-12 | D04452 | 20 | | | | D41701P | 10 | | | 001-099 |
| 0044 | 24 | GK | | | 34-0 | 73-21-12 | D04452 | 20 | | | | D41701P | 33 | | | 115-199 |
| 0045 | 24 | GK | | | 35-0 | 73-21-12 | D04452 | 19 | | | | D41701P | 9 | | | 001-099 |
| 0045 | 24 | GK | | | 35-0 | 73-21-12 | D04452 | 19 | | | | D41701P | 32 | | | 115-199 |
| 0046Y | 20 | QB | | | 41-0 | 27-41-31 | D41709P | 9 | | | | SP00399 | | 9 | | 001-099 |
| 0048 | 22 | GA | | | 16-0 | 27-62-11 | D40501P | 27 | | | | D04452 | 3 | | | 001-099 |
| 0048 | 22 | GA | | | 15-0 | 27-62-11 | D40501P | 27 | | | | D04452 | 3 | | | 115-199 |
| 0049 | 20 | GA | | | 16-0 | 27-62-11 | D40501P | 28 | | | | D04452 | 1 | | | 001-099 |
| 0049 | 22 | GA | | | 15-0 | 27-62-11 | D40501P | 28 | | | | D04452 | 1 | | | 115-199 |
| 0050 | 22 | GA | | | 16-0 | 27-62-11 | D40501P | 29 | | | | D04452 | 2 | | | 001-099 |
| 0050 | 22 | GA | | | 15-0 | 27-62-11 | D40501P | 29 | | | | D04452 | 2 | | | 115-199 |
| 0055 | 22 | GA | | | 5-0 | 27-62-11 | TB0100X | A004 | BJ | | | D40501P | 34 | | | ALL |
| 0060Y | 22 | QB | | | 36-0 | 27-41-11 | D41709P | 7 | | | | SM00006 | | 9 | | ALL |
| 0066Y | 22 | QB | | | 36-0 | 27-41-11 | D41709P | 10 | | | | SM00005 | | 9 | | ALL |
| 0073Y | 22 | QB | | | 36-0 | 27-41-11 | D41709P | 8 | | | | SM00004 | | 9 | | ALL |
| 0075Y | 22 | QB | | | 36-0 | 27-41-11 | D41709P | 12 | | | | SM00003 | | 9 | | ALL |
| 0084Y | 22 | QB | | | 41-0 | 27-41-11 | D41709P | 2 | | | | TB0065Y | A006 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 15

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2355 | 286N2355 | | | | CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL L (continued) | | | | | | | | | | | |
| 0084Y | 22 | | QB | | 40-0 | 27-41-11 | D41709P | | 2 | | TB0065Y | A006 | BJ | | 115-199 | |
| 0085Y | 22 | | QB | | 41-0 | 27-41-11 | D41709P | | 3 | | TB0065Y | C006 | BJ | | 001-099 | |
| 0085Y | 22 | | QB | | 40-0 | 27-41-11 | D41709P | | 3 | | TB0065Y | C006 | BJ | | 115-199 | |
| 0086Y | 22 | | QB | | 41-0 | 27-41-11 | D41709P | | 4 | | TB0065Y | A007 | BJ | | 001-099 | |
| 0086Y | 22 | | QB | | 40-0 | 27-41-11 | D41709P | | 4 | | TB0065Y | A007 | BJ | | 115-199 | |
| 0087 | 20 | | GA | | 6-0 | 33-13-52 | D02542 | | 1 | | TB0101Z | 9 | BJ | | ALL | |
| 0088 | 20 | | GA | | 6-0 | 33-13-52 | D02542 | | 2 | | GD02519 | AC.. | 2 | | ALL | |
| 0089 | 22 | | GA | | 6-0 | 27-48-11 | D02542 | | 3 | | GD02519 | ST.. | 2 | | ALL | |
| 0090 | 22 | | GA | | 6-0 | 27-48-11 | D02542 | | 9 | | GD02519 | AC.. | 2 | | ALL | |
| 0091 | 22 | | GA | | 16-0 | 32-42-12 | D04452 | | 11 | | D40495P | 12 | | | 001-099 | |
| 0091 | 24 | | GK | | 16-0 | 32-42-12 | D04452 | | 11 | | D40495P | 12 | | | 115-199 | |
| 0092 | 22 | | GA | | 54-0 | 32-42-12 | D04452 | | 12 | | D42414P | 1 | | | 001-099 | |
| 0092 | 24 | | GK | | 35-0 | 32-42-12 | D04452 | | 12 | | D41701P | 29 | | | 115-199 | |
| 0093 | 22 | | GA | | 54-0 | 32-42-12 | D04452 | | 14 | | D42414P | 2 | | | 001-099 | |
| 0093 | 24 | | GK | | 35-0 | 32-42-12 | D04452 | | 14 | | D41701P | 30 | | | 115-199 | |
| 0094 | 22 | | GA | | 54-0 | 32-42-12 | D04452 | | 15 | | D42414P | 3 | | | 001-099 | |
| 0094 | 24 | | GK | | 35-0 | 32-42-12 | D04452 | | 15 | | D41701P | 31 | | | 115-199 | |
| 0095Y | 22 | | QB | | 5-0 | 27-41-11 | SM00003 | | 9 | | SP00169 | | 9 | | ALL | |
| 0096Y | 22 | | QB | | 8-0 | 27-41-11 | SM00003 | | 9 | | SP00025 | | 9 | | ALL | |
| 0097Y | 22 | | QB | | 5-0 | 27-41-11 | SM00004 | | 9 | | SP00167 | | 9 | | ALL | |
| 0098Y | 22 | | QB | | 8-0 | 27-41-11 | SM00004 | | 9 | | SP00027 | | 9 | | ALL | |
| 0099Y | 22 | | QB | | 5-0 | 27-41-11 | SM00005 | | 9 | | SP00171 | | 9 | | ALL | |
| 0100Y | 22 | | QB | | 8-0 | 27-41-11 | SM00005 | | 9 | | SP00029 | | 9 | | ALL | |
| 0101Y | 22 | | QB | | 5-0 | 27-41-11 | SM00006 | | 9 | | SP00165 | | 9 | | ALL | |
| 0102Y | 22 | | QB | | 8-0 | 27-41-11 | SM00006 | | 9 | | SP00031 | | 9 | | ALL | |
| 0103 | 24 | | GK | | 48-0 | 24-22-22 | D41713P | | 3 | | SP00075 | | 9 | | 001-099 | |
| 0103 | 24 | | GK | | 45-0 | 24-22-22 | D41713P | | 3 | | SP00075 | | 9 | | 115-199 | |
| 0104 | 24 | | GK | | 5-0 | 24-22-22 | D04452 | | 4 | | SP00075 | | 9 | | 001-099 | |
| 0104 | 24 | | GK | | 4-0 | 24-22-22 | D04452 | | 4 | | SP00075 | | 9 | | 115-199 | |
| 0105 | 24 | | GK | | 2-0 | 24-22-22 | D04452 | | 5 | | GD02749 | DC.. | 2 | | 001-099 | |
| 0105 | 24 | | GK | | 3-0 | 24-22-22 | D04452 | | 5 | | GD02749 | DC.. | 2 | | 115-199 | |
| 2005B | 24 | | GL | AJ | 33-0 | 22-32-13 | D00399 | | M | | D41711P | 11 | | | 001-099 | |
| 2005B | 24 | | GL | AJ | 32-0 | 22-32-13 | D00399 | | M | | D41711P | 11 | | | 115-199 | |
| 2005R | 24 | | GL | AJ | 0-0 | 22-32-13 | D00399 | | N | | D41711P | 12 | | | ALL | |
| 3005B | 20 | | GC | AL | 32-0 | 22-32-13 | SM00001 | | 9 | | D41711P | 15 | | | ALL | |
| 3005R | 20 | | GC | AL | 0-0 | 22-32-13 | D00399 | | D | | D41711P | 16 | | | ALL | |
| 3005Y | 20 | | GC | AL | 0-0 | 22-32-13 | D00399 | | A | | D41711P | 17 | | | ALL | |
| A-A | | | | | 0-0 | 27-41-11 | S00334 | | NO | | SP00171 | | 9 | | ALL | |
| A-B | | | | | 0-0 | 27-41-11 | S00334 | | C | | SP00169 | | 9 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 16

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2355 | 286N2355 | | | CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL L (continued) | | | | | | | | | | | |
| | B-A | | | | 0-0 | 27-41-11 | S10234 | | NO | | SP00029 | | 9 | | ALL |
| | B-B | | | | 0-0 | 27-41-11 | S10234 | | C | | SP00025 | | 9 | | ALL |
| | C-A | | | | 0-0 | 27-41-11 | S00335 | | NO | | SP00165 | | 9 | | ALL |
| | C-B | | | | 0-0 | 27-41-11 | S00335 | | C | | SP00167 | | 9 | | ALL |
| | D-A | | | | 0-0 | 27-41-11 | S10235 | | NO | | SP00031 | | 9 | | ALL |
| | D-B | | | | 0-0 | 27-41-11 | S10235 | | C | | SP00027 | | 9 | | ALL |
| W2356 | 286N2356 | | | P11 TO E/E BAY, POWER DISTR - CAT R(B) | | | | | | | | | | | |
| | 0001 | 22 | GA | | 27-0 | 31-51-11 | D40620P | | 1 | | D40714P | | 1 | | ALL |
| | 0002 | 24 | GK | | 41-0 | 33-42-12 | D40620P | | 2 | | D41472P | | 33 | | 001-099 |
| | 0002 | 20 | GA | | 41-0 | 33-42-12 | D40620P | | 2 | | D41472P | | 33 | | 115-199 |
| | 0003 | 22 | GA | | 41-0 | 38-14-11 | D40620P | | 3 | | D41472P | | 7 | | ALL |
| | 0004 | 24 | GK | | 33-0 | SPARE | D40620P | | 4 | | D40718P | | 4 | | 001-099 |
| | 0004 | 24 | GK | | 34-0 | SPARE | D40620P | | 4 | | D40718P | | 4 | | 115-199 |
| | 0005 | 24 | GK | | 33-0 | 21-61-21 | D40620P | | 5 | | D40718P | | 5 | | 001-099 |
| | 0005 | 24 | GK | | 34-0 | 21-61-21 | D40620P | | 5 | | D40718P | | 5 | | 115-199 |
| | 0006 | 24 | GK | | 33-0 | 21-61-31 | D40620P | | 6 | | D40718P | | 6 | | 001-099 |
| | 0006 | 24 | GK | | 34-0 | 21-61-31 | D40620P | | 6 | | D40718P | | 6 | | 115-199 |
| | 0007 | 22 | GA | | 34-0 | 35-11-13 | D40620P | | 7 | | D40718P | | 7 | | 115-199 |
| | 0008 | 22 | GA | | 33-0 | 33-51-11 | D40620P | | 8 | | D40718P | | 13 | | 001-099 |
| | 0008 | 22 | GA | | 34-0 | 33-51-11 | D40620P | | 8 | | D40718P | | 13 | | 115-199 |
| | 0009 | 22 | GA | | 33-0 | 33-51-11 | D40620P | | 9 | | D40718P | | 14 | | 001-099 |
| | 0009 | 22 | GA | | 34-0 | 33-51-11 | D40620P | | 9 | | D40718P | | 14 | | 115-199 |
| | 0010 | 24 | GK | | 33-0 | 36-11-41 | D40620P | | 26 | | D40718P | | 2 | | 001-099 |
| | 0010 | 24 | GK | | 34-0 | 36-11-41 | D40620P | | 26 | | D40718P | | 2 | | 115-199 |
| | 0011 | 22 | GA | | 33-0 | 32-09-12 | D40620P | | 11 | | D40718P | | 11 | | 001-099 |
| | 0011 | 22 | GA | | 34-0 | 32-09-12 | D40620P | | 11 | | D40718P | | 11 | | 115-199 |
| | 0012 | 20 | GA | | 33-0 | 29-21-32 | D40620P | | 12 | | D40718P | | 12 | | 001-099 |
| | 0012 | 20 | GA | | 34-0 | 29-21-32 | D40620P | | 12 | | D40718P | | 12 | | 115-199 |
| | 0013 | 24 | GK | | 35-0 | SPARE | D40620P | | 13 | | D40812P | | 1 | | 001-099 |
| | 0013 | 24 | GK | | 36-0 | SPARE | D40620P | | 13 | | D40812P | | 1 | | 115-199 |
| | 0014 | 22 | GA | | 35-0 | 33-26-11 | D40620P | | 14 | | D40716P | | 4 | | 001-002, 115-199 |
| | 0014 | 22 | GA | | 35-0 | SPARE | D40620P | | 14 | | D40716P | | 4 | | 003-099 |
| | 0015 | 22 | GA | | 35-0 | 26-16-21 | D40620P | | 15 | | D40716P | | 5 | | ALL |
| | 0016 | 24 | GK | | 33-0 | 21-61-11 | D40620P | | 16 | | D40718P | | 16 | | 001-099 |
| | 0016 | 24 | GK | | 34-0 | 21-61-11 | D40620P | | 16 | | D40718P | | 16 | | 115-199 |
| | 0017 | 24 | GK | | 33-0 | 21-61-21 | D40620P | | 17 | | D40718P | | 17 | | 001-099 |
| | 0017 | 24 | GK | | 34-0 | 21-61-21 | D40620P | | 17 | | D40718P | | 17 | | 115-199 |
| | 0018 | 18 | GA | | 33-0 | 30-34-22 | D40620P | | 18 | 18 | D40718P | | 23 | 18 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 17

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2356 | 286N2356 | | | | P11 TO E/E BAY, POWER DISTR - CAT R(B) (continued) | | | | | | | | | | | |
| 0019 | 20 | | GA | | 35-0 | 21-51-21 | | D41970P | | 4 | | D40812P | | 9 | | 001-099 |
| 0019 | 20 | | GA | | 37-0 | 21-51-21 | | D41970P | | 4 | | D40812P | | 9 | | 115-199 |
| 0020 | 22 | | CQ | | 48-0 | 34-22-26 | | D41970P | | 5 | | D41408P | | 23 | | 002 |
| 0020 | 20 | | GA | | 35-0 | SPARE | | D41970P | | 5 | | D41408P | | 23 | | 115-199 |
| 0021 | 24 | | GK | | 33-0 | 36-21-11 | | D40620P | | 21 | | D40718P | | 20 | | 001-099 |
| 0021 | 24 | | GK | | 34-0 | 36-21-11 | | D40620P | | 21 | | D40718P | | 20 | | 115-199 |
| 0022 | 22 | | GA | | 35-0 | 27-48-21 | | D41970P | | 2 | | D40812P | | 4 | | 001-099 |
| 0022 | 22 | | GA | | 37-0 | 27-48-21 | | D41970P | | 2 | | D40812P | | 4 | | 115-199 |
| 0023 | 22 | | GA | | 35-0 | SPARE | | D40620P | | 23 | | D40812P | | 5 | | 001-099 |
| 0023 | 22 | | GA | | 36-0 | SPARE | | D40620P | | 23 | | D40812P | | 5 | | 115-199 |
| 0024 | 24 | | GK | | 33-0 | SPARE | | D40620P | | 24 | | D40718P | | 24 | | 001-099 |
| 0024 | 24 | | GK | | 34-0 | SPARE | | D40620P | | 24 | | D40718P | | 24 | | 115-199 |
| 0025 | 22 | | GA | | 33-0 | 76-11-21 | | D40620P | | 25 | | D40718P | | 25 | | 001-099 |
| 0025 | 22 | | GA | | 34-0 | 76-11-21 | | D40620P | | 25 | | D40718P | | 25 | | 115-199 |
| 0027 | 22 | | GA | | 27-0 | SPARE | | D40620P | | 27 | | D40714P | | 3 | | 115-199 |
| 0028 | 22 | | GA | | 30-0 | 28-21-11 | | D40620P | | 28 | | D41424P | | 3 | | 001-099 |
| 0028 | 22 | | GA | | 33-0 | 28-21-11 | | D40620P | | 28 | | D41424P | | 3 | | 115-199 |
| 0029 | 24 | | GK | | 27-0 | SPARE | | D40620P | | 29 | | D40714P | | 2 | | 115-199 |
| 0030 | 22 | | GA | | 33-0 | 77-11-11 | | D40620P | | 30 | | D40718P | | 30 | | 001-099 |
| 0030 | 22 | | GA | | 34-0 | 77-11-11 | | D40620P | | 30 | | D40718P | | 30 | | 115-199 |
| 0031 | 22 | | GA | | 33-0 | 30-34-22 | | D40620P | | 31 | | D40718P | | 31 | | 001-099 |
| 0033 | 24 | | GK | | 33-0 | 21-61-31 | | D40620P | | 33 | | D40718P | | 33 | | 001-099 |
| 0033 | 24 | | GK | | 34-0 | 21-61-31 | | D40620P | | 33 | | D40718P | | 33 | | 115-199 |
| 0034 | 24 | | GK | | 35-0 | 21-25-11 | | D40620P | | 34 | | D40716P | | 1 | | ALL |
| 0036 | 20 | | GA | | 34-0 | SPARE | | D41970P | | 6 | | D40718P | | 36 | | 115-199 |
| 0037 | 16 | | GA | | 15-0 | 33-26-11 | | D41472P | | 15 | 16 | D40718P | | 22 | 16 | 001-099 |
| 0037 | 20 | | GA | | 34-0 | 25-31-21 | | D41970P | | 7 | | D40718P | | 37 | | 115-199 |
| 0049 | 20 | | GA | | 35-0 | 21-51-13 | | D41970P | | 9 | | D40716P | | 18 | | 001-099 |
| 0050 | 24 | | GK | | 33-0 | SPARE | | D40620P | | 50 | | D40718P | | 34 | | 001-099 |
| 0050 | 24 | | GK | | 34-0 | SPARE | | D40620P | | 50 | | D40718P | | 34 | | 115-199 |
| 0054 | 22 | | GA | | 26-0 | SPARE | | D41472P | | 46 | | D40716P | | 2 | | 115-199 |
| 0055 | 22 | | GA | | 26-0 | SPARE | | D41472P | | 6 | | D40716P | | 3 | | 115-199 |
| 0056 | 20 | | GA | | 19-0 | 33-31-41 | | S00357 | | 3 | C | SP00246 | | 9 | | 001-099 |
| 0057 | 20 | | GA | | 15-0 | 33-31-41 | | SP00248 | | 9 | | SP00246 | | 9 | | 001-099 |
| 0058 | 20 | | GA | | 17-0 | 33-31-41 | | SP00250 | | 9 | | SP00246 | | 9 | | 001-099 |
| 0060 | 20 | | GA | | 33-0 | 21-51-22 | | D40718P | | 26 | | D40620P | | 36 | | 001-099 |
| 0060 | 20 | | GA | | 34-0 | 21-51-22 | | D40718P | | 26 | | D40620P | | 36 | | 115-199 |
| 0064 | 22 | | GA | | 33-0 | 30-34-22 | | D40620P | | 31 | | D40718P | | 31 | | 115-199 |
| 0065 | 18 | | GA | | 33-0 | 30-34-22 | | D40620P | | 18 | 18 | D40718P | | 35 | 18 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 18

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2356 | | 286N2356 | | | | P11 TO E/E BAY, POWER DISTR - CAT R(B) (continued) | | | | | | | | | |
| 0073 | 20 | GA | | | 41-0 | 25-31-11 | D40620P | 10 | | | D41472P | 53 | | | 001-099 |
| 0074 | 20 | GA | | | 3-0 | 31-51-11 | D40714P | 4 | | | GD02300 | AC.. | E | | ALL |
| 0089 | 24 | GK | | | 15-0 | 33-51-11 | D40718P | 10 | | | SP01280 | | 9 | | ALL |
| 0092 | 22 | GA | | | 12-0 | 33-21-51 | D41472P | 48 | | | D41408P | 41 | | | 001-099 |
| 0092 | 22 | GA | | | 13-0 | 33-21-51 | D41472P | 48 | | | D41408P | 41 | | | 115-199 |
| 0113 | 16 | GA | | | 35-0 | 78-34-61 | D40620P | 32 | 16 | | D41408P | 19 | 16 | | 001-002, 115-199 |
| 0113 | 16 | GA | | | 34-0 | 78-34-61 | D40620P | 32 | 16 | | D41408P | 19 | 16 | | 003-099 |
| 0201 | 20 | GA | | | 33-0 | 36-11-41 | D40620P | 35 | | | D40718P | 35 | | | 001-099 |
| 0203 | 20 | GA | | | 27-0 | SPARE | D40620P | 52 | | | D40714P | 9 | | | 115-199 |
| 0204 | 20 | GA | | | 27-0 | SPARE | D40620P | 53 | | | D40714P | 10 | | | 115-199 |
| 0205 | 24 | GK | | | 33-0 | SPARE | D40620P | 54 | | | D40718P | 1 | | | 001-099 |
| 0205 | 20 | GA | | | 27-0 | SPARE | D40620P | 54 | | | D40714P | 11 | | | 115-199 |
| 0206 | 24 | GK | | | 33-0 | SPARE | D40620P | 55 | | | D40718P | 45 | | | 001-099 |
| 0206 | 20 | GA | | | 27-0 | SPARE | D40620P | 55 | | | D40714P | 12 | | | 115-199 |
| 0208 | 24 | GK | | | 33-0 | 30-33-11 | D40620P | 45 | | | D40718P | 18 | | | 001-099 |
| 0208 | 24 | GK | | | 34-0 | 30-33-11 | D40620P | 45 | | | D40718P | 18 | | | 115-199 |
| 0209 | 20 | GA | | | 33-0 | 74-31-21 | D40620P | 46 | | | D40718P | 19 | | | 001-099 |
| 0209 | 20 | GA | | | 34-0 | 74-31-21 | D40620P | 46 | | | D40718P | 19 | | | 115-199 |
| 0211 | 24 | GK | | | 35-0 | SPARE | D40620P | 48 | | | D40812P | 2 | | | 001-099 |
| 0211 | 24 | GK | | | 36-0 | SPARE | D40620P | 48 | | | D40812P | 2 | | | 115-199 |
| 0212 | 24 | GK | | | 33-0 | 36-11-22 | D40620P | 49 | | | D40718P | 28 | | | ALL |
| 0213 | 20 | GA | | | 41-0 | SPARE | D40620P | 38 | | | D41472P | 52 | | | 001-099 |
| 0213 | 20 | GA | | | 34-0 | 36-11-41 | D40620P | 38 | | | D40718P | 38 | | | 115-199 |
| 0214 | 20 | GA | | | 33-0 | 29-21-32 | D40620P | 39 | | | D40718P | 39 | | | 001-099 |
| 0214 | 20 | GA | | | 34-0 | 29-21-32 | D40620P | 39 | | | D40718P | 39 | | | 115-199 |
| 0215 | 24 | GK | | | 33-0 | 21-61-11 | D40620P | 40 | | | D40718P | 21 | | | 001-099 |
| 0215 | 24 | GK | | | 34-0 | 21-61-11 | D40620P | 40 | | | D40718P | 21 | | | 115-199 |
| 0216 | 22 | GA | | | 35-0 | 26-16-21 | D40620P | 41 | | | D40716P | 16 | | | ALL |
| 0217 | 20 | GA | | | 35-0 | 21-51-13 | D40620P | 42 | | | D40716P | 11 | | | 001-099 |
| 0217 | 20 | GA | | | 35-0 | SPARE | D40620P | 42 | | | D40716P | 11 | | | 115-199 |
| 0218 | 20 | GA | | | 35-0 | SPARE | D40620P | 43 | | | D40716P | 12 | | | ALL |
| 0234 | 22 | GA | | | 15-0 | SPARE | D41472P | 3 | | | D40718P | 29 | | | 001-099 |
| 0234 | 22 | GA | | | 16-0 | SPARE | D40718P | 29 | | | D41472P | 3 | | | 115-199 |
| 0244 | 22 | GA | | | 15-0 | SPARE | D41472P | 4 | | | D40718P | 32 | | | 001-099 |
| 0244 | 22 | GA | | | 16-0 | SPARE | D41472P | 4 | | | D40718P | 32 | | | 115-199 |
| 0245 | 20 | GA | | | 16-0 | SPARE | D41472P | 5 | | | D40718P | 40 | | | 115-199 |
| 0247 | 22 | GA | | | 15-0 | 38-14-11 | D41472P | 8 | | | D40718P | 41 | | | 001-099 |
| 0247 | 22 | GA | | | 16-0 | 38-14-11 | D41472P | 8 | | | D40718P | 41 | | | 115-199 |
| 0248 | 18 | GA | | | 12-0 | SPARE | D41476P | 1 | | | D41408P | 28 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 19

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2356 | 286N2356 | | | | P11 TO E/E BAY, POWER DISTR - CAT R(B) (continued) | | | | | | | | | | | |
| 0249 | 18 | | GA | | 12-0 | SPARE | D41476P | | 2 | | | D41408P | 29 | | | 115-199 |
| 0250 | 18 | | GA | | 12-0 | 24-51-25 | D41476P | | 3 | | | D41408P | 30 | | | ALL |
| 0251 | 18 | | GA | | 12-0 | SPARE | D41476P | | 4 | | | D41408P | 31 | | | 115-199 |
| 0252 | 20 | | GA | | 15-0 | 33-22-11 | D41472P | | 9 | | | D40718P | 42 | | | 115-199 |
| 0253 | 22 | | GA | | 13-0 | SPARE | D41472P | | 10 | | | D41408P | 43 | | | 115-199 |
| 0254 | 24 | | GK | | 15-0 | 33-21-11 | D41472P | | 11 | | | D40718P | 44 | | | ALL |
| 0255 | 20 | | GA | | 25-0 | 33-31-11 | D41472P | | 12 | | | D40716P | 15 | | | 001-099 |
| 0255 | 20 | | GA | | 26-0 | 33-31-11 | D41472P | | 12 | | | D40716P | 15 | | | 115-199 |
| 0256 | 22 | | GA | | 15-0 | 33-26-31 | D41472P | | 13 | | | D40718P | 46 | | | ALL |
| 0257 | 20 | | GA | | 40-0 | 33-31-41 | D41472P | | 14 | | | S00357 | 2 | C | | 001-099 |
| 0257 | 20 | | GA | | 15-0 | 33-31-41 | D41472P | | 14 | | | D40718P | 47 | | | 115-199 |
| 0258 | 22 | | GA | | 16-0 | 33-26-11 | D41472P | | 15 | | | D40718P | 22 | | | 115-199 |
| 0259 | 22 | | GA | | 15-0 | 35-11-13 | D41472P | | 40 | | | D40718P | 49 | | | 115-199 |
| 0260 | 16 | | GA | | 15-0 | 33-26-11 | D41472P | | 41 | 16 | | D40718P | 50 | 16 | | 001-099 |
| 0260 | 22 | | GA | | 15-0 | 33-26-11 | D41472P | | 41 | | | D40718P | 50 | | | 115-199 |
| 0261 | 24 | | GK | | 30-0 | 33-22-11 | D41472P | | 16 | | | D41424P | 11 | | | 001-099 |
| 0261 | 22 | | GA | | 32-0 | 33-22-11 | D41472P | | 16 | | | D41424P | 10 | | | 115-199 |
| 0262 | 22 | | GA | | 13-0 | SPARE | D41472P | | 17 | | | D41408P | 1 | | | 115-199 |
| 0263 | 16 | | GA | | 12-0 | 33-24-11 | D41476P | | 14 | | | D41408P | 1 | | | 001-099 |
| 0263 | 16 | | GA | | 13-0 | 33-24-11 | D41472P | | 18 | 16 | | D41408P | 2 | 16 | | 115-199 |
| 0264 | 22 | | GA | | 12-0 | 33-24-11 | D41472P | | 19 | | | D41408P | 3 | | | 001-099 |
| 0264 | 22 | | GA | | 13-0 | 33-24-11 | D41472P | | 19 | | | D41408P | 3 | | | 115-199 |
| 0266 | 20 | | GA | | 12-0 | 33-24-11 | D41472P | | 21 | | | D41408P | 5 | | | 001-099 |
| 0266 | 16 | | GA | | 13-0 | 33-24-11 | D41472P | | 21 | 16 | | D41408P | 5 | 16 | | 115-199 |
| 0267 | 24 | | GK | | 12-0 | 33-24-11 | D41472P | | 22 | | | D41408P | 6 | | | 001-099 |
| 0267 | 22 | | GA | | 13-0 | 33-24-11 | D41472P | | 22 | | | D41408P | 6 | | | 115-199 |
| 0268 | 16 | | GA | | 25-0 | 33-24-11 | D41476P | | 15 | | | D40716P | 7 | 16 | | 001-099 |
| 0268 | 16 | | GA | | 26-0 | 33-24-11 | D41472P | | 23 | 16 | | D40716P | 7 | 16 | | 115-199 |
| 0269 | 22 | | GA | | 25-0 | 33-24-11 | D41472P | | 24 | | | D40716P | 9 | | | 001-099 |
| 0269 | 22 | | GA | | 26-0 | 33-24-11 | D41472P | | 24 | | | D40716P | 9 | | | 115-199 |
| 0270 | 18 | | GA | | 26-0 | SPARE | D41472P | | 25 | 18 | | D40716P | 10 | 18 | | 115-199 |
| 0271 | 22 | | GA | | 13-0 | 33-22-11 | D41472P | | 26 | | | D41408P | 7 | | | 115-199 |
| 0272 | 22 | | GA | | 13-0 | SPARE | D41472P | | 27 | | | D41408P | 8 | | | 115-199 |
| 0273 | 22 | | GA | | 12-0 | 33-21-51 | D41472P | | 28 | | | D41408P | 9 | | | 001-099 |
| 0273 | 22 | | GA | | 13-0 | 33-21-51 | D41472P | | 28 | | | D41408P | 9 | | | 115-199 |
| 0274 | 22 | | GA | | 12-0 | 33-21-51 | D41472P | | 29 | | | D41408P | 10 | | | 001-099 |
| 0274 | 22 | | GA | | 13-0 | 33-21-51 | D41408P | | 10 | | | D41472P | 29 | | | 115-199 |
| 0275 | 22 | | GA | | 12-0 | SPARE | D41472P | | 30 | | | D41408P | 11 | | | 001-099 |
| 0275 | 22 | | GA | | 13-0 | 33-27-31 | D41472P | | 30 | | | D41408P | 11 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 20

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2356 | | 286N2356 | | | | P11 TO E/E BAY, POWER DISTR - CAT R(B) (continued) | | | | | | | | | |
| 0276 | 22 | GA | | | 12-0 | SPARE | D41472P | 31 | | | D41408P | 12 | | | 001-099 |
| 0276 | 22 | GA | | | 13-0 | 33-27-31 | D41472P | 31 | | | D41408P | 12 | | | 115-199 |
| 0277 | 22 | GA | | | 15-0 | 33-26-31 | D41472P | 32 | | | D40718P | 53 | | | ALL |
| 0278 | 20 | GA | | | 12-0 | 33-42-12 | D41472P | 34 | | | D41408P | 14 | | | 001-099 |
| 0278 | 20 | GA | | | 13-0 | 33-42-12 | D41472P | 34 | | | D41408P | 14 | | | 115-199 |
| 0279 | 20 | GA | | | 12-0 | 33-42-12 | D41472P | 35 | | | D41408P | 16 | | | 001-099 |
| 0279 | 20 | GA | | | 13-0 | 33-42-12 | D41472P | 35 | | | D41408P | 16 | | | 115-199 |
| 0280 | 20 | GA | | | 13-0 | 33-42-12 | D41472P | 44 | | | D41408P | 17 | | | 115-199 |
| 0281 | 22 | GA | | | 30-0 | 27-51-21 | D41424P | 30 | | | D41970P | 1 | | | 001-099 |
| 0281 | 22 | GA | | | 33-0 | 27-51-21 | D41424P | 30 | | | D41970P | 1 | | | 115-199 |
| 0282 | 22 | GA | | | 15-0 | 33-51-11 | D40718P | 15 | | | D41472P | 20 | | | 001-099 |
| 0282 | 22 | GA | | | 16-0 | 33-51-11 | D41472P | 20 | | | D40718P | 15 | | | 115-199 |
| 0283 | 22 | GA | | | 28-0 | SPARE | D41424P | 4 | | | D40812P | 6 | | | 115-199 |
| 0284 | 18 | GA | | | 12-0 | SPARE | D41408P | 15 | | | D41476P | 5 | | | 115-199 |
| 0285 | 18 | GA | | | 12-0 | SPARE | D41408P | 22 | | | D41476P | 6 | | | 115-199 |
| 0286 | 18 | GA | | | 12-0 | SPARE | D41408P | 27 | | | D41476P | 7 | | | 115-199 |
| 0287 | 16 | GA | | | 30-0 | 28-21-11 | D41424P | 4 | | | D41476P | 18 | | | 001-099 |
| 0287 | 16 | GA | | | 32-0 | 28-21-11 | D41424P | 5 | 16 | | D41472P | 37 | 16 | | 115-199 |
| 0288 | 16 | GA | | | 30-0 | 28-21-11 | D41424P | 6 | | | D41476P | 17 | | | 001-099 |
| 0288 | 16 | GA | | | 32-0 | 28-21-11 | D41424P | 6 | | | D41472P | 36 | 16 | | 115-199 |
| 0289 | 16 | GA | | | 30-0 | 28-21-11 | D41424P | 8 | | | D41476P | 19 | | | 001-099 |
| 0289 | 16 | GA | | | 32-0 | 28-21-11 | D41424P | 7 | 16 | | D41472P | 38 | 16 | | 115-199 |
| 0290 | 22 | GA | | | 25-0 | 28-21-21 | D41424P | 7 | | | D40812P | 7 | | | 001-099 |
| 0290 | 20 | GA | | | 27-0 | 28-21-21 | D41424P | 8 | | | D40812P | 7 | | | 115-199 |
| 0291 | 20 | GA | | | 25-0 | 28-21-21 | D41424P | 9 | | | D40812P | 8 | | | 001-099 |
| 0291 | 20 | GA | | | 28-0 | 28-21-21 | D41424P | 9 | | | D40812P | 8 | | | 115-199 |
| 0292 | 20 | GA | | | 12-0 | 33-42-21 | D41472P | 39 | | | D41408P | 21 | | | 001-099 |
| 0292 | 20 | GA | | | 13-0 | 33-42-21 | D41472P | 39 | | | D41408P | 35 | | | 115-199 |
| 0293 | 22 | GA | | | 15-0 | 33-22-11 | D41472P | 18 | | | D40718P | 27 | | | 001-099 |
| 0293 | 22 | GA | | | 15-0 | SPARE | D41472P | 42 | | | D40718P | 51 | | | 115-199 |
| 0294 | 22 | GA | | | 15-0 | 33-22-11 | D41472P | 43 | | | D40718P | 52 | | | ALL |
| 0295 | 16 | GA | | | 12-0 | 33-21-11 | D41476P | 8 | | | D41408P | 32 | | | ALL |
| 0296 | 16 | GA | | | 12-0 | 33-21-11 | D41476P | 9 | | | D41408P | 33 | | | ALL |
| 0297 | 18 | GA | | | 17-0 | 33-31-41 | D41476P | 10 | | | S00355 | 5 | C | | 001-099 |
| 0297 | 18 | GA | | | 12-0 | 33-31-41 | D41476P | 10 | | | D41408P | 34 | | | 115-199 |
| 0298 | 24 | GK | | | 15-0 | 33-21-31 | D40718P | 54 | | | D41472P | 45 | | | ALL |
| 0308 | 20 | GA | | | 24-0 | SPARE | D40718P | 8 | | | D41424P | 11 | | | 115-199 |
| 0309 | 20 | GA | | | 24-0 | SPARE | D40718P | 9 | | | D41424P | 12 | | | 115-199 |
| 0321 | 24 | GK | | | 30-0 | 27-51-31 | D41970P | 8 | | | D41424P | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 21

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | Description | From | To | | | | | | | | | |
|------------|-------------|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2356 | 286N2356 | | P11 TO E/E BAY, POWER DISTR - CAT R(B) (continued) | | | | | | | | | | | |
| 0321 | 22 | GA | | 33-0 | 27-51-31 | D41424P | 18 | | | D41970P | 8 | | | 115-199 |
| 0324 | 20 | GA | | 13-0 | SPARE | D41472P | 54 | | | D41408P | 24 | | | 115-199 |
| 0325 | 20 | GA | | 13-0 | SPARE | D41472P | 55 | | | D41408P | 25 | | | 115-199 |
| 0330 | 22 | GA | | 19-0 | SPARE | D41408P | 18 | | | D40716P | 8 | | | 115-199 |
| 0331 | 22 | GA | | 19-0 | SPARE | D41408P | | CAP | Y | D40716P | 14 | | | 115-199 |
| 0332 | 22 | GA | | 12-0 | SPARE | D41408P | 20 | | | D41476P | 11 | | | 115-199 |
| 0343 | 20 | GA | | 24-0 | SPARE | D40718P | 43 | | | D41424P | 13 | | | 115-199 |
| 0344 | 22 | GA | | 30-0 | 29-31-11 | D40620P | 22 | | | D41424P | 14 | | | 001-099 |
| 0344 | 22 | GA | | 33-0 | 29-31-11 | D40620P | 22 | | | D41424P | 14 | | | 115-199 |
| 0345 | 20 | GA | | 23-0 | SPARE | D40718P | 45 | | | D41424P | 24 | | | 115-199 |
| 0355 | 18 | GA | | 6-0 | 25-29-11 | D40718P | 55 | 18 | | D00878 | =P | D | | 001-099 |
| 0355 | 20 | GA | | 23-0 | SPARE | D40718P | 55 | | | D41424P | 15 | | | 115-199 |
| 0356 | 18 | GA | | 2-0 | 25-29-11 | D00878 | =G | D | | GD02460 | ST.. | E | | 001-099 |
| 0357 | 18 | GA | | 2-0 | 25-29-11 | D00878 | =N | D | | GD00925 | AC.. | E | | 001-099 |
| 0602 | 22 | GA | | 35-0 | 26-18-11 | D40620P | 20 | | | D40812P | 12 | | | 001-099 |
| 0602 | 22 | GA | | 36-0 | 26-18-11 | D40620P | 20 | | | D40812P | 12 | | | 115-199 |
| 0603 | 22 | GA | | 35-0 | 26-18-11 | D40620P | 44 | | | D40812P | 10 | | | 001-099 |
| 0603 | 22 | GA | | 36-0 | 26-18-11 | D40620P | 44 | | | D40812P | 10 | | | 115-199 |
| 0605 | 20 | GA | | 35-0 | SPARE | D40620P | | CAP | Y | D40716P | 20 | | | 115-199 |
| 0606 | 18 | GA | | 23-0 | 28-22-11 | D41424P | 1 | | | D41408P | 36 | | | 001-099 |
| 0606 | 18 | GA | | 25-0 | 28-22-11 | D41424P | 1 | | | D41408P | 36 | | | 115-199 |
| 0607 | 18 | GA | | 23-0 | 28-22-11 | D41424P | 2 | | | D41408P | 37 | | | 001-099 |
| 0607 | 18 | GA | | 25-0 | 28-22-11 | D41424P | 2 | | | D41408P | 37 | | | 115-199 |
| 0610 | 16 | GA | | 12-0 | 33-21-31 | D41476P | 12 | | | D41408P | 38 | | | ALL |
| 0611 | 16 | GA | | 12-0 | 33-21-31 | D41476P | 13 | | | D41408P | 39 | | | ALL |
| 0612 | 18 | GA | | 12-0 | SPARE | D41476P | 14 | | | D41408P | 40 | | | 115-199 |
| 0613 | 22 | GA | | 33-0 | SPARE | D40620P | 35 | | | D41424P | 17 | | | 115-199 |
| 0614 | 22 | GA | | 41-0 | SPARE | D40620P | 37 | | | D41472P | 47 | | | ALL |
| A-K | | | | 0-0 | 33-31-41 | L00384 | =P | | | SP00246 | | 9 | | 001-099 |
| A-L | | | | 0-0 | 33-31-41 | L00335 | =P | | | SP00248 | | 9 | | 001-099 |
| A-M | | | | 0-0 | 33-31-41 | L00336 | =P | | | SP00250 | | 9 | | 001-099 |
| B-K | | | | 0-0 | 33-31-41 | L00384 | =G | | | GD00159 | AC.. | E | | 001-099 |
| B-L | | | | 0-0 | 33-31-41 | L00335 | =G | | | GD00160 | AC.. | E | | 001-099 |
| B-M | | | | 0-0 | 33-31-41 | L00336 | =G | | | GD00161 | AC.. | E | | 001-099 |
| W2357 | 286N2357 | | CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL R | | | | | | | | | | | |
| 0001 | 22 | GA | | 40-0 | 22-11-22 | D41703P | 1 | | | TB0065X | A003 | BJ | | 001-099 |
| 0001 | 22 | GA | | 41-0 | 22-11-22 | D41703P | 1 | | | TB0065X | A003 | BJ | | 115-199 |
| 0002 | 22 | GA | | 40-0 | 22-11-22 | D41703P | 6 | | | TB0065X | B003 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 22

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity | | | | | | | | |
|------------|-------------|--|-------|----------|-------------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2357 | 286N2357 | CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL R (continued) | | | | | | | | | | | |
| 0002 | 22 | GA | 41-0 | 22-11-22 | D41703P | 6 | | | TB0065X | B003 | BJ | | 115-199 |
| 0003 | 22 | GA | 1-0 | 22-11-22 | TB0065X | C003 | BJ | | TB0065X | C004 | BJ | | ALL |
| 0004 | 20 | GA | 34-0 | 27-62-11 | D40495P | 1 | | | D41703P | 2 | | | 001-099 |
| 0004 | 20 | GA | 35-0 | 27-62-11 | D40495P | 1 | | | D41703P | 2 | | | 115-199 |
| 0005 | 20 | GA | 34-0 | 27-62-11 | D40495P | 2 | | | D41703P | 3 | | | 001-099 |
| 0005 | 20 | GA | 35-0 | 27-62-11 | D40495P | 2 | | | D41703P | 3 | | | 115-199 |
| 0006 | 22 | GA | 34-0 | 22-12-21 | D40495P | 3 | | | D41703P | 7 | | | 001-099 |
| 0006 | 22 | GA | 35-0 | 22-12-21 | D40495P | 3 | | | D41703P | 7 | | | 115-199 |
| 0007 | 22 | GA | 34-0 | 22-12-21 | D40495P | 4 | | | D41703P | 8 | | | 001-099 |
| 0007 | 22 | GA | 35-0 | 22-12-21 | D40495P | 4 | | | D41703P | 8 | | | 115-199 |
| 0008Y | 22 | QB | 34-0 | 27-41-21 | D41707P | 1 | | | SM00004 | | 9 | | 001-099 |
| 0008Y | 22 | QB | 32-0 | 27-41-21 | D41707P | 1 | | | SM00004 | | 9 | | 115-199 |
| 0009Y | 22 | QB | 34-0 | 27-41-21 | D41707P | 2 | | | SM00002 | | 9 | | 001-099 |
| 0009Y | 22 | QB | 32-0 | 27-41-21 | D41707P | 2 | | | SM00002 | | 9 | | 115-199 |
| 0011Y | 22 | QB | 34-0 | 27-41-21 | D41707P | 4 | | | SM00003 | | 9 | | 001-099 |
| 0011Y | 22 | QB | 32-0 | 27-41-21 | D41707P | 4 | | | SM00003 | | 9 | | 115-199 |
| 0013Y | 22 | QB | 34-0 | 27-41-21 | D41707P | 6 | | | SM00001 | | 9 | | 001-099 |
| 0013Y | 22 | QB | 32-0 | 27-41-21 | D41707P | 6 | | | SM00001 | | 9 | | 115-199 |
| 0014 | 24 | GK | 36-0 | 73-21-22 | D41703P | 9 | | | D04454 | 13 | | | 001-099 |
| 0014 | 24 | GK | 35-0 | 73-21-22 | D41715P | 6 | | | D04454 | 13 | | | 115-199 |
| 0015 | 24 | GK | 36-0 | 73-21-22 | D41703P | 10 | | | D04454 | 14 | | | 001-099 |
| 0015 | 24 | GK | 35-0 | 73-21-22 | D41715P | 7 | | | D04454 | 14 | | | 115-199 |
| 0016 | 22 | GA | 41-0 | 27-48-11 | D02496 | 8 | | | D41707P | 10 | | | 001-099 |
| 0016 | 22 | GA | 40-0 | 27-48-11 | D02496 | 8 | | | D41707P | 10 | | | 115-199 |
| 0017 | 22 | GA | 41-0 | 27-48-11 | D02496 | 6 | | | D41707P | 11 | | | 001-099 |
| 0017 | 22 | GA | 40-0 | 27-48-11 | D02496 | 6 | | | D41707P | 11 | | | 115-199 |
| 0018 | 22 | GA | 41-0 | 27-48-11 | D02496 | 7 | | | D41707P | 12 | | | 001-099 |
| 0018 | 22 | GA | 40-0 | 27-48-11 | D02496 | 7 | | | D41707P | 12 | | | 115-199 |
| 0023 | 22 | GA | 46-0 | 32-42-12 | D04454 | 2 | | | D42412P | 1 | | | 001-099 |
| 0023 | 24 | GK | 35-0 | 32-42-12 | D04454 | 2 | | | D41715P | 1 | | | 115-199 |
| 0024 | 22 | GA | 46-0 | 32-42-12 | D04454 | 5 | | | D42412P | 3 | | | 001-099 |
| 0024 | 24 | GK | 35-0 | 32-42-12 | D04454 | 5 | | | D41715P | 3 | | | 115-199 |
| 0025 | 22 | GA | 45-0 | 32-42-12 | D40495P | 17 | | | D42412P | 4 | | | 001-099 |
| 0025 | 22 | GA | 33-0 | 32-42-12 | D40495P | 17 | | | D41715P | 4 | | | 115-199 |
| 0026 | 22 | GA | 40-0 | 27-32-21 | SP00185 | | 9 | | D41707P | 17 | | | ALL |
| 0027 | 22 | GA | 40-0 | 27-32-21 | SP00187 | | 9 | | D41707P | 18 | | | ALL |
| 0028 | 22 | GA | 45-0 | 32-42-12 | D40495P | 18 | | | D42412P | 5 | | | 001-099 |
| 0028 | 22 | GA | 33-0 | 32-42-12 | D40495P | 18 | | | D41715P | 5 | | | 115-199 |
| 0029Y | 22 | QB | 45-0 | 27-41-21 | TB0065Y | C005 | BJ | | D41707P | 8 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 23

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|---|-----------------|----|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| | | GA | CO TY | Fam | FT-IN | Diagram | | | | | | | | | |
| W2357 | 286N2357 | | | | | | | | | | | | | | |
| CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL R (continued) | | | | | | | | | | | | | | | |
| 0030 | 22 | GA | | | 46-0 | 32-42-12 | D42412P | | 2 | | D04454 | | 4 | | 001-099 |
| 0030 | 24 | GK | | | 35-0 | 32-42-12 | D41715P | | 2 | | D04454 | | 4 | | 115-199 |
| 0032 | 20 | GA | | | 15-0 | 33-13-52 | D02496 | | 1 | | TB0101Z | | 9 | BJ | ALL |
| 0033 | 20 | GA | | | 4-0 | 33-13-52 | D02496 | | 2 | | GD02519 | AC.. | 2 | | ALL |
| 0034 | 22 | GA | | | 4-0 | 27-48-11 | D02496 | | 3 | | GD02519 | ST.. | 2 | | ALL |
| 0035 | 22 | GA | | | 4-0 | 27-48-11 | D02496 | | 9 | | GD02519 | AC.. | 2 | | ALL |
| 0036Y | 22 | QB | | | 45-0 | 27-41-21 | TB0065Y | A005 | BJ | | D41707P | | 7 | | ALL |
| 0038 | 22 | GA | | | 13-0 | 32-42-12 | D04454 | | 1 | | D40495P | | 6 | | 001-099 |
| 0038 | 24 | GK | | | 13-0 | 32-42-12 | D04454 | | 1 | | D40495P | | 6 | | 115-199 |
| 0039 | 24 | GK | | | 41-0 | 31-51-42 | D41707P | | 20 | | D04454 | | 9 | | 001-099 |
| 0039 | 24 | GK | | | 39-0 | 31-51-42 | D41707P | | 20 | | D04454 | | 9 | | 115-199 |
| 0042 | 20 | GA | | | 2-0 | 31-51-42 | D04454 | | 10 | | GD02749 | DC.. | 2 | | ALL |
| 0047 | 24 | GK | | | 39-0 | 31-51-41 | D41707P | | 21 | | D40495P | | 20 | | 001-099 |
| 0047 | 24 | GK | | | 40-0 | 31-51-41 | D41707P | | 21 | | D40495P | | 20 | | 115-199 |
| 0055Y | 22 | QB | | | 13-0 | 27-41-21 | SM00001 | | 9 | | SP00181 | | 9 | | ALL |
| 0056Y | 22 | QB | | | 9-0 | 27-41-21 | SM00001 | | 9 | | SP00017 | | 9 | | ALL |
| 0057Y | 22 | QB | | | 13-0 | 27-41-21 | SM00002 | | 9 | | SP00179 | | 9 | | ALL |
| 0058Y | 22 | QB | | | 9-0 | 27-41-21 | SM00002 | | 9 | | SP00019 | | 9 | | ALL |
| 0059Y | 22 | QB | | | 13-0 | 27-41-21 | SM00003 | | 9 | | SP00183 | | 9 | | ALL |
| 0060Y | 22 | QB | | | 9-0 | 27-41-21 | SM00003 | | 9 | | SP00021 | | 9 | | ALL |
| 0061Y | 22 | QB | | | 13-0 | 27-41-21 | SM00004 | | 9 | | SP00177 | | 9 | | ALL |
| 0062Y | 22 | QB | | | 9-0 | 27-41-21 | SM00004 | | 9 | | SP00023 | | 9 | | ALL |
| 0107 | 24 | GK | | | 5-0 | 24-22-22 | D04454 | | 7 | | SP00075 | | 9 | | 001-099 |
| 0107 | 24 | GK | | | 4-0 | 24-22-22 | D04454 | | 7 | | SP00075 | | 9 | | 115-199 |
| 0108 | 24 | GK | | | 2-0 | 24-22-22 | D04454 | | 8 | | GD02749 | DC.. | 2 | | ALL |
| 0109 | 24 | GK | | | 46-0 | 21-31-21 | D04454 | | 11 | | D42412P | | 6 | | 001-099 |
| 0109 | 24 | GK | | | 4-0 | 21-31-21 | D04454 | | 11 | | SP00085 | | 9 | | 115-199 |
| A-A | | | | | 0-0 | 27-41-21 | S00337 | | NO | | SP00021 | | 9 | | 001-099 |
| A-A | | | | | 2-0 | 27-41-21 | S00337 | | NO | | SP00021 | | 9 | | 115-199 |
| A-B | | | | | 0-0 | 27-41-21 | S00337 | | C | | SP00017 | | 9 | | ALL |
| B-A | | | | | 0-0 | 27-41-21 | S10236 | | NO | | SP00183 | | 9 | | ALL |
| B-B | | | | | 0-0 | 27-41-21 | S10236 | | C | | SP00181 | | 9 | | ALL |
| C-A | | | | | 0-0 | 27-41-21 | S00338 | | NO | | SP00023 | | 9 | | ALL |
| C-B | | | | | 0-0 | 27-41-21 | S00338 | | C | | SP00019 | | 9 | | ALL |
| D-A | | | | | 0-0 | 27-41-21 | S10237 | | NO | | SP00177 | | 9 | | ALL |
| D-B | | | | | 0-0 | 27-41-21 | S10237 | | C | | SP00179 | | 9 | | ALL |
| W2358 | 286N2358 | | | | | | | | | | | | | | |
| P11 TO E/E BAY - POWER DISTR CAT S(A) | | | | | | | | | | | | | | | |
| 0001 | 18 | GA | | | 47-0 | 23-31-11 | D40838P | | 10 | | D40734P | | 10 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 24

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2358 | 286N2358 | | | P11 TO E/E BAY - POWER DISTR CAT S(A) (continued) | | | | | | | | | | | |
| 0002 | 22 | | GA | | 44-0 | 28-21-11 | D40838P | | 3 | | D41426P | | 6 | | 001-099 |
| 0002 | 22 | | GA | | 48-0 | 28-21-11 | D40838P | | 3 | | D41426P | | 6 | | 115-199 |
| 0003 | 22 | | GA | | 47-0 | SPARE | D40622P | | 3 | | D40734P | | 5 | | 115-199 |
| 0004 | 22 | | GA | | 47-0 | SPARE | D40622P | | 24 | | D40734P | | 6 | | 115-199 |
| 0005 | 12 | | GA | | 34-11 | 28-25-11 | D40838P | | 6 | | D41968P | | 15 | | ALL |
| 0006 | 24 | | GK | | 36-0 | 28-25-11 | D40838P | | 30 | | D41968P | | 18 | | 001-099 |
| 0006 | 22 | | GA | | 36-0 | 28-25-11 | D40838P | | 30 | | D41968P | | 18 | | 115-199 |
| 0007 | 22 | | GA | | 34-0 | 34-31-31 | D40622P | | 7 | | D41884P | | 7 | | 001-099 |
| 0007 | 22 | | GA | | 33-0 | 34-31-31 | D40622P | | 7 | | D41884P | | 7 | | 115-199 |
| 0008 | 20 | | GA | | 34-0 | 34-24-11 | D40622P | | 8 | | D41884P | | 8 | | 001-099 |
| 0008 | 20 | | GA | | 33-0 | 34-24-11 | D40622P | | 8 | | D41884P | | 8 | | 115-199 |
| 0009 | 24 | | GK | | 34-0 | 34-24-11 | D40622P | | 9 | | D41884P | | 9 | | 001-099 |
| 0009 | 24 | | GK | | 33-0 | 34-24-11 | D40622P | | 9 | | D41884P | | 9 | | 115-199 |
| 0010 | 20 | | GA | | 34-0 | 22-31-12 | D40622P | | 10 | | D41884P | | 10 | | 001-099 |
| 0010 | 20 | | GA | | 33-0 | 22-31-12 | D40622P | | 10 | | D41884P | | 10 | | 115-199 |
| 0011 | 20 | | GA | | 34-0 | 22-11-32 | D40622P | | 11 | | D41884P | | 11 | | 001-099 |
| 0011 | 20 | | GA | | 33-0 | 22-11-32 | D40622P | | 11 | | D41884P | | 11 | | 115-199 |
| 0012 | 22 | | GA | | 47-0 | 23-42-11 | D40838P | | 12 | | D40734P | | 12 | | ALL |
| 0013 | 22 | | GA | | 42-0 | SPARE | D40622P | | 13 | | D40728P | | 23 | | 115-199 |
| 0014 | 22 | | GA | | 36-0 | 34-51-11 | D40622P | | 14 | | D43011P | | 1 | | 001-099 |
| 0014 | 22 | | GA | | 161-0 | 34-51-11 | D40622P | | 14 | | D41962P | | 1 | | 115-199 |
| 0015 | 24 | | GK | | 146-0 | 28-25-11 | D42238P | | 8 | | D40838P | | 32 | | 001-099 |
| 0015 | 22 | | GA | | 163-0 | 28-25-11 | D42238P | | 8 | | D40838P | | 32 | | 115-199 |
| 0016 | 22 | | GA | | 8-0 | 21-58-12 | D40838P | | 17 | | TB0115Y | A005 | BJ | | ALL |
| 0017 | 22 | | GA | | 120-0 | 28-25-11 | D42238P | | 11 | | D41968P | | 17 | | 001-099 |
| 0018 | 18 | | GA | | 48-0 | 30-31-11 | D40622P | | 18 | 18 | D41426P | | 18 | 18 | 115-199 |
| 0019 | 22 | | GA | | 120-0 | 28-25-11 | D42238P | | 12 | | D41968P | | 20 | | 001-099 |
| 0019 | 22 | | GA | | 137-0 | 28-25-11 | D42238P | | 12 | | D41968P | | 20 | | 115-199 |
| 0020 | 22 | | GA | | 42-0 | SPARE | D40838P | | 2 | | D40728P | | 8 | | 115-199 |
| 0022 | 22 | | GA | | 36-0 | SPARE | D40622P | | 22 | | D41964P | | 12 | | 115-199 |
| 0024 | 20 | | GA | | 27-0 | 24-51-14 | D41968P | | 9 | | D41966P | | 4 | | ALL |
| 0025 | 24 | | GK | | 42-0 | 34-12-11 | D40622P | | 25 | | D40728P | | 25 | | ALL |
| 0026 | 20 | | GA | | 22-0 | 38-13-11 | D41968P | | 21 | | D40728P | | 1 | | 001-099 |
| 0027 | 24 | | GK | | 42-0 | 21-58-12 | D40838P | | 5 | | D40728P | | 2 | | ALL |
| 0028 | 24 | | GK | | 22-0 | SPARE | D41968P | | 13 | | D40728P | | 13 | | 001-099 |
| 0029 | 24 | | GK | | 131-0 | 21-51-11 | D40728P | | 9 | | D42218P | | 1 | | 001-099 |
| 0031 | 22 | | GA | | 44-0 | 28-22-21 | D40838P | | 18 | | D41426P | | 1 | | 001-099 |
| 0031 | 22 | | GA | | 48-0 | 28-22-21 | D40838P | | 18 | | D41426P | | 1 | | 115-199 |
| 0033 | 16 | | GA | | 42-0 | 75-31-11 | D40838P | | 4 | | D40728P | | 21 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 25

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2358 | 286N2358 | | | | P11 TO E/E BAY - POWER DISTR CAT S(A) (continued) | | | | | | | | | | | |
| 0035 | 24 | | GK | | 42-0 | 78-36-11 | | D40838P | 13 | | | D40728P | 28 | | | ALL |
| 0045 | 20 | | GA | | 163-0 | 21-51-13 | | D40838P | 20 | | | D42238P | 11 | | | 115-199 |
| 0046 | 20 | | GA | | 36-0 | SPARE | | D40622P | 16 | | | D43011P | 2 | | | 001-099 |
| 0046 | 20 | | GA | | 161-0 | SPARE | | D40622P | 16 | | | D41962P | 6 | | | 115-199 |
| 0047 | 22 | | GA | | 48-0 | 27-51-31 | | D40838P | 26 | | | D41426P | 7 | | | 115-199 |
| 0048 | 20 | | GA | | 163-0 | 21-51-23 | | D40838P | 21 | | | D42238P | 15 | | | 115-199 |
| 0052 | 22 | | GA | | 44-0 | 27-51-31 | | D40622P | 27 | | | D41426P | 2 | | | 001-099 |
| 0054 | 22 | | PA | | 42-0 | 34-61-15 | | D40622P | 36 | | | D41884P | 6 | | | 115-199 |
| 0066 | 22 | | GA | | 35-0 | 27-21-12 | | D40622P | 24 | | | D41964P | 1 | | | 005-099 |
| 0067 | 22 | | GA | | 42-0 | 32-61-11 | | D40838P | 2 | | | D40728P | 14 | | | 003-099 |
| 0068 | 22 | | GA | | 36-0 | 27-21-12 | | D40622P | 29 | | | D41964P | 1 | | | 001-004 |
| 0102 | 16 | | GA | | 47-0 | 23-12-11 | | D40622P | 21 | | | D40734P | 4 | | | ALL |
| 0112 | 22 | | GA | | 35-0 | 27-09-11 | | D40622P | 2 | | | D41964P | 2 | | | 001-099 |
| 0112 | 22 | | GA | | 36-0 | 27-09-11 | | D40622P | 2 | | | D41964P | 2 | | | 115-199 |
| 0114 | 22 | | GA | | 35-0 | 27-09-11 | | D40622P | 4 | | | D41964P | 4 | | | 001-099 |
| 0114 | 22 | | GA | | 36-0 | 27-09-11 | | D40622P | 4 | | | D41964P | 4 | | | 115-199 |
| 0115 | 20 | | GA | | 161-0 | SPARE | | D40622P | 26 | | | D41962P | 5 | | | 115-199 |
| 0123 | 22 | | GA | | 24-0 | SPARE | | D40728P | 14 | | | D41426P | 13 | | | 115-199 |
| 0124 | 22 | | GA | | 24-0 | SPARE | | D40728P | 15 | | | D41426P | 11 | | | 115-199 |
| 0125 | 22 | | GA | | 24-0 | SPARE | | D40728P | 16 | | | D41426P | 12 | | | 115-199 |
| 0134 | 22 | | GA | | 42-0 | 30-21-11 | | D40728P | 27 | | | D40838P | 9 | | | ALL |
| 0206 | 20 | | GA | | 42-0 | SPARE | | D40838P | 23 | | | D40728P | 6 | | | 115-199 |
| 0207 | 16 | | GA | | 146-0 | 49-61-11 | | D40838P | 8 | | | D42238P | 7 | | | 001-099 |
| 0207 | 16 | | GA | | 163-0 | 49-61-11 | | D40838P | 8 | | | D42238P | 14 | | | 115-199 |
| 0212 | 22 | | GA | | 42-0 | 34-22-16 | | D40622P | 13 | | | D40728P | 12 | | | 001-099 |
| 0212 | 22 | | GA | | 42-0 | 34-22-16 | | D40622P | 12 | | | D40728P | 12 | | | 115-199 |
| 0241 | 24 | | GK | | 47-0 | 27-51-61 | | D40622P | 31 | | | D41966P | 1 | | | 001-099 |
| 0241 | 22 | | GA | | 47-0 | 27-51-61 | | D40622P | 31 | | | D41966P | 1 | | | 115-199 |
| 0242 | 24 | | GK | | 47-0 | 27-51-61 | | D40622P | 32 | | | D41966P | 2 | | | 001-099 |
| 0242 | 22 | | GA | | 47-0 | 27-51-61 | | D40622P | 32 | | | D41966P | 2 | | | 115-199 |
| 0243 | 24 | | GK | | 47-0 | 27-51-61 | | D40622P | 33 | | | D41966P | 3 | | | 001-099 |
| 0243 | 22 | | GA | | 47-0 | 27-51-61 | | D40622P | 33 | | | D41966P | 3 | | | 115-199 |
| 0244 | 24 | | GK | | 36-0 | 27-51-61 | | D40622P | 34 | | | D41968P | 14 | | | 001-099 |
| 0244 | 22 | | GA | | 36-0 | 27-51-61 | | D40622P | 34 | | | D41968P | 14 | | | 115-199 |
| 0245 | 24 | | GK | | 36-0 | 27-51-61 | | D40622P | 35 | | | D41968P | 16 | | | 001-099 |
| 0245 | 22 | | GA | | 36-0 | 27-51-61 | | D40622P | 35 | | | D41968P | 16 | | | 115-199 |
| 0325 | 22 | | GA | | 48-0 | 32-44-11 | | D40838P | 25 | | | D41426P | 5 | | | 115-199 |
| 0332 | 22 | | GA | | 148-0 | 32-42-11 | | D40728P | 32 | | | D42218P | 2 | | | 115-199 |
| 0333 | 22 | | GA | | 148-0 | 32-42-11 | | D40728P | 33 | | | D42218P | 3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 26

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2358 | | 286N2358 | | | | P11 TO E/E BAY - POWER DISTR CAT S(A) (continued) | | | | | | | | | |
| 0334 | 22 | GA | | | 148-0 | 32-42-11 | D40728P | 34 | | | D42218P | 4 | | | 115-199 |
| 0335 | 22 | GA | | | 148-0 | 32-42-11 | D40728P | 35 | | | D42218P | 5 | | | 115-199 |
| 0336 | 22 | GA | | | 148-0 | 32-42-11 | D40728P | 36 | | | D42218P | 6 | | | 115-199 |
| 0349 | 20 | GA | | | 42-0 | 74-31-11 | D40622P | 37 | | | D40728P | 29 | | | ALL |
| 0401 | 12 | HA | | | 43-0 | 29-21-31 | D40838P | 1 | | | D41426P | 7 | | | 001-099 |
| 0401 | 12 | HA | | | 47-4 | 29-21-31 | D40838P | 1 | | | SP01524 | | 9 | | 115-199 |
| 0406 | 24 | GK | | | 44-0 | 30-31-11 | D40622P | 12 | | | D41426P | 5 | | | 001-099 |
| 0416 | 22 | GA | | | 29-0 | 26-16-21 | D04426 | 1 | | | D41968P | 3 | | | ALL |
| 0417 | 22 | GA | | | 110-0 | 26-16-21 | D41262J | 1 | | | D41968P | 2 | | | 001-099 |
| 0417 | 22 | GA | | | 111-0 | 26-16-21 | D04428 | 1 | | | D41968P | 2 | | | 115-199 |
| 0418 | 22 | GA | | | 110-0 | 26-16-21 | D04430 | 1 | | | D41968P | 1 | | | ALL |
| 0419 | 22 | GA | | | 22-0 | 26-16-21 | D41968P | 8 | | | D40728P | 19 | | | ALL |
| 0420 | 22 | GA | | | 22-0 | 26-16-21 | D41968P | 7 | | | D40728P | 20 | | | ALL |
| 0421 | 22 | GA | | | 22-0 | 26-16-21 | D41968P | 6 | | | D40728P | 10 | | | ALL |
| 0422 | 22 | GA | | | 22-0 | 26-16-21 | D41968P | 5 | | | D40728P | 22 | | | ALL |
| 0423 | 20 | GA | | | 4-0 | 26-16-21 | D41256J | 2 | | | GD01900 | AC.. | E | | 001-099 |
| 0423 | 20 | GA | | | 3-0 | 26-16-21 | D04424 | 2 | | | GD01900 | AC.. | E | | 115-199 |
| 0424 | 20 | GA | | | 4-0 | 26-16-21 | D41256J | 3 | | | GD01946 | ST.. | E | | 001-099 |
| 0424 | 20 | GA | | | 3-0 | 26-16-21 | D04424 | 3 | | | GD01946 | ST.. | E | | 115-199 |
| 0425 | 22 | GA | | | 30-0 | 26-16-21 | D41256J | 1 | | | D41968P | 4 | | | 001-099 |
| 0425 | 22 | GA | | | 29-0 | 26-16-21 | D04424 | 1 | | | D41968P | 4 | | | 115-199 |
| 0426 | 20 | GA | | | 3-0 | 26-16-21 | D04426 | 3 | | | GD01946 | ST.. | E | | ALL |
| 0427 | 22 | GA | | | 17-0 | 26-16-21 | D04434 | 2 | | | D40728P | 30 | | | ALL |
| 0428 | 20 | GA | | | 3-0 | 26-16-21 | D04434 | 3 | | | GD01940 | DC.. | E | | ALL |
| 0429 | 20 | GA | | | 6-0 | 26-16-21 | D41262J | 2 | | | GD01920 | AC.. | E | | 001-099 |
| 0429 | 20 | GA | | | 5-0 | 26-16-21 | D04428 | 2 | | | GD01920 | AC.. | E | | 115-199 |
| 0430 | 20 | GA | | | 6-0 | 26-16-21 | D41262J | 3 | | | GD01924 | ST.. | E | | 001-099 |
| 0430 | 20 | GA | | | 5-0 | 26-16-21 | D04428 | 3 | | | GD01924 | ST.. | E | | 115-199 |
| 0431 | 20 | GA | | | 5-0 | 26-16-21 | D04430 | 2 | | | GD01920 | AC.. | E | | ALL |
| 0432 | 20 | GA | | | 5-0 | 26-16-21 | D04430 | 3 | | | GD01924 | ST.. | E | | ALL |
| 0433 | 20 | GA | | | 5-0 | 26-16-21 | D04432 | 3 | | | GD01922 | DC.. | E | | 001-099 |
| 0433 | 20 | GA | | | 4-0 | 26-16-21 | D04432 | 3 | | | GD01922 | DC.. | E | | 115-199 |
| 0434 | 22 | GA | | | 121-0 | 26-16-21 | D04432 | 2 | | | D40728P | 31 | | | ALL |
| 0435 | 20 | GA | | | 3-0 | 26-16-21 | D04426 | 2 | | | GD01900 | AC.. | E | | ALL |
| 0437 | 24 | GK | | | 148-0 | 29-33-11 | D40728P | 37 | | | D42218P | 7 | | | 115-199 |
| 0438 | 22 | GA | | | 148-0 | SPARE | D40728P | 38 | | | D42218P | 8 | | | 115-199 |
| 0439 | 22 | GA | | | 148-0 | SPARE | D40728P | 39 | | | D42218P | 9 | | | 115-199 |
| 0501 | 22 | GA | | | 42-0 | SPARE | D40622P | 17 | | | D40728P | 17 | | | 115-199 |
| 0507 | 22 | GA | | | 24-0 | SPARE | D40728P | 3 | | | D41426P | 2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 27

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2358 | 286N2358 | | | | P11 TO E/E BAY - POWER DISTR CAT S(A) (continued) | | | | | | | | | | | | |
| 0508 | 22 | | GA | | 44-0 | 28-22-21 | | D40838P | | 14 | | D41426P | | 3 | | 001-099 | |
| 0508 | 22 | | GA | | 48-0 | 28-22-21 | | D40838P | | 14 | | D41426P | | 3 | | 115-199 | |
| 0510 | 24 | | GK | | 22-0 | SPARE | | D41968P | | 10 | | D40728P | | 4 | | 115-199 | |
| 0511 | 22 | | GA | | 22-0 | 38-13-11 | | D41968P | | 11 | | D40728P | | 5 | | 001-099 | |
| 0511 | 20 | | GA | | 22-0 | 38-13-11 | | D41968P | | 11 | | D40728P | | 5 | | 115-199 | |
| 0512 | 22 | | GA | | 22-0 | 38-13-11 | | D41968P | | 12 | | D40728P | | 11 | | 001-099 | |
| 0512 | 20 | | GA | | 22-0 | 38-13-11 | | D41968P | | 12 | | D40728P | | 11 | | 115-199 | |
| 0513 | 20 | | GA | | 22-0 | SPARE | | D41968P | | 13 | | D40728P | | 13 | | 115-199 | |
| 0522 | 22 | | GA | | 24-0 | SPARE | | D41426P | | 17 | | D40728P | | 24 | | 115-199 | |
| 0528 | 22 | | GA | | 44-0 | 29-11-11 | | D40838P | | 28 | | D41426P | | 4 | | 001-099 | |
| 0528 | 22 | | GA | | 48-0 | 29-11-11 | | D40838P | | 28 | | D41426P | | 4 | | 115-199 | |
| 0531 | 20 | | GA | | 42-0 | 80-11-11 | | D40838P | | 7 | | D40728P | | 18 | | ALL | |
| 0532 | 22 | | GA | | 146-0 | 28-25-21 | | D40838P | | 16 | | D42238P | | 3 | | 001-099 | |
| 0532 | 22 | | GA | | 163-0 | 28-25-21 | | D40838P | | 16 | | D42238P | | 3 | | 115-199 | |
| 0601 | 22 | | GA | | 42-0 | 32-61-11 | | D40838P | | 31 | | D40728P | | 26 | | ALL | |
| 0606 | 22 | | GA | | 47-0 | SPARE | | D40622P | | 30 | | D41966P | | 8 | | 115-199 | |
| 0608 | 22 | | GA | | 36-0 | SPARE | | D40622P | | 28 | | D41964P | | 8 | | 115-199 | |
| 0609 | 22 | | GA | | 36-0 | 27-21-12 | | D40622P | | 29 | | D41964P | | 9 | | 115-199 | |
| 0610 | 22 | | GA | | 36-0 | SPARE | | D40622P | | 23 | | D41964P | | 10 | | 115-199 | |
| 0617 | 20 | | GA | | 33-0 | SPARE | | D40622P | | 20 | | D41884P | | 2 | | 115-199 | |
| 0700 | 22 | | GA | | 146-0 | 24-33-12 | | D40838P | | 19 | | D42238P | | 4 | | 001-099 | |
| 0701 | 24 | | GK | | 146-0 | 24-33-12 | | D42238P | | 1 | | D40838P | | 11 | | 001-099 | |
| 0702 | 22 | | GA | | 146-0 | 24-33-12 | | D42238P | | 2 | | D40838P | | 22 | | 001-099 | |
| 0703 | 22 | | GA | | 146-0 | 24-33-12 | | D42238P | | 6 | | D40838P | | 24 | | 001-099 | |
| 0704 | 22 | | GA | | 146-0 | 24-33-12 | | D42238P | | 9 | | D40838P | | 29 | | 001-099 | |
| 0710 | 22 | | GA | | 146-0 | 24-33-12 | | D40838P | | 27 | | D42238P | | 10 | | 001-099 | |
| 0715 | 22 | | GA | | 146-0 | 24-33-12 | | D40838P | | 15 | | D42238P | | 5 | | 001-099 | |
| W2359 | 286N2359 | | | | CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL C | | | | | | | | | | | | |
| 0001 | 22 | | GA | | 40-0 | 22-11-32 | | D41705P | | 1 | | TB0065X | A004 | BJ | | ALL | |
| 0004 | 22 | | GA | | 1-0 | 22-11-32 | | TB0065X | B004 | BJ | | TB0065X | D003 | BJ | | ALL | |
| 0005 | 22 | | GA | | 34-0 | 22-12-31 | | D40503P | | 2 | | D41705P | | 8 | | 001-099 | |
| 0005 | 22 | | GA | | 36-0 | 22-12-31 | | D40503P | | 2 | | D41705P | | 8 | | 115-199 | |
| 0006 | 22 | | GA | | 34-0 | 22-12-31 | | D40503P | | 1 | | D41705P | | 7 | | 001-099 | |
| 0006 | 22 | | GA | | 36-0 | 22-12-31 | | D40503P | | 1 | | D41705P | | 7 | | 115-199 | |
| 0007 | 22 | | GA | | 40-0 | 22-11-32 | | TB0065X | D004 | BJ | | D41705P | | 6 | | ALL | |
| 0008 | 22 | | GA | | 18-0 | 31-31-31 | | D40503P | | 24 | | TB0101X | A007 | BJ | | 115-199 | |
| 0009 | 22 | | GA | | 48-0 | SPARE | | D40503P | | 11 | | D40927P | | 3 | | 115-199 | |
| 0010 | 22 | | GA | | 48-0 | SPARE | | D40503P | | 10 | | D40927P | | 4 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 28

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice Effectivity |
| W2359 | 286N2359 | | | CAPTAIN AND 1ST OFFICER CONTROL WHEEL TO E/E BAY-CHANNEL C (continued) | | | | | | | | | | |
| 2005B | 22 | GB | AN | | 48-0 | 31-31-31 | D40503P | 20 | | | D40927P | 2 | | 115-199 |
| 2005R | 22 | GB | AN | | 0-0 | 31-31-31 | D40503P | 19 | | | D40927P | 1 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2350

Page 29 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2360 | 286N2360 | | | P11 TO E/E BAY - POWER DISTR-CAT S(B) | | | | | | | | | | | |
| 0001 | 22 | | GA | | 34-0 | SPARE | D40624P | | | 1 | D40738P | | | 1 | 001-002, 115-199 |
| 0001 | 22 | | GA | | 35-0 | SPARE | D40624P | | | 1 | D40738P | | | 1 | 003-099 |
| 0002 | 16 | | GA | | 35-0 | 35-21-11 | D41972P | | | 32 | D40738P | | | 16 | ALL |
| 0003 | 24 | | GK | | 35-0 | 35-21-11 | D41972P | | | 3 | D40738P | | | 3 | 001-099 |
| 0003 | 22 | | GA | | 35-0 | 35-21-11 | D41972P | | | 3 | D40738P | | | 3 | 115-199 |
| 0004 | 24 | | GK | | 35-0 | 35-21-11 | D41972P | | | 10 | D40738P | | | 2 | 001-099 |
| 0004 | 22 | | GA | | 35-0 | 35-21-11 | D41972P | | | 10 | D40738P | | | 2 | 115-199 |
| 0005 | 16 | | GA | | 35-0 | 75-31-11 | D41972P | | | 1 | D40738P | | | 20 | ALL |
| 0006 | 24 | | GK | | 35-0 | 30-31-12 | D41972P | | | 8 | D40738P | | | 12 | 115-199 |
| 0007 | 16 | | GA | | 35-0 | 35-21-11 | D41972P | | | 27 | D40738P | | | 18 | ALL |
| 0009 | 24 | | GK | | 35-0 | 78-36-21 | D41972P | | | 9 | D40738P | | | 9 | 115-199 |
| 0013 | 22 | | GA | | 27-0 | 31-51-12 | D40624P | | | 13 | D40736P | | | 3 | ALL |
| 0014 | 20 | | GA | | 4-0 | 31-51-12 | D40736P | | | 4 | GD02301 | AC.. | E | | 001-002, 115-199 |
| 0014 | 20 | | GA | | 3-0 | 31-51-12 | D40736P | | | 4 | GD02301 | AC.. | E | | 003-099 |
| 0016 | 24 | | GK | | 35-0 | 78-36-21 | D41972P | | | 2 | D40738P | | | 15 | 003-099 |
| 0024 | 24 | | GK | | 35-0 | 78-36-21 | D41972P | | | 12 | D40738P | | | 9 | 001-002 |
| 0024 | 24 | | GK | | 35-0 | SPARE | D41972P | | | 12 | D40738P | | | 9 | 003-099 |
| 0026 | 22 | | GA | | 35-0 | 30-21-11 | D41972P | | | 14 | D40738P | | | 14 | ALL |
| 0029 | 22 | | GA | | 42-0 | 27-09-11 | D40624P | | | 29 | D41902P | | | 9 | 001-002, 115-199 |
| 0029 | 22 | | GA | | 43-0 | 27-09-11 | D40624P | | | 29 | D41902P | | | 9 | 003-099 |
| 0030 | 22 | | GA | | 42-0 | 27-09-11 | D40624P | | | 30 | D41902P | | | 10 | 001-002, 115-199 |
| 0030 | 22 | | GA | | 43-0 | 27-09-11 | D40624P | | | 30 | D41902P | | | 10 | 003-099 |
| 0035 | 20 | | GA | | 35-0 | 29-22-11 | D41972P | | | 6 | D40738P | | | 6 | 115-199 |
| 0050 | 24 | | GK | | 35-0 | 30-31-12 | D41972P | | | 8 | D40738P | | | 6 | 001-099 |
| 0051 | 20 | | GA | | 32-0 | 23-32-01 | D41972P | | | 13 | SP26001 | | | 9 | 001-099 |
| 0051 | 20 | | GA | | 30-0 | 23-32-01 | D41972P | | | 13 | SP26001 | | | 9 | 115-199 |
| 0120 | 22 | | GA | | 42-0 | 27-32-11 | D40624P | | | 20 | D41902P | | | 2 | 001-002, 115-199 |
| 0120 | 22 | | GA | | 43-0 | 27-32-11 | D40624P | | | 20 | D41902P | | | 2 | 003-099 |
| 0208 | 20 | | GA | | 34-0 | 74-31-21 | D40624P | | | 38 | D40738P | | | 8 | 001-002, 115-199 |
| 0208 | 20 | | GA | | 35-0 | 74-31-21 | D40624P | | | 38 | D40738P | | | 8 | 003-099 |
| 0311 | 20 | | GA | | 35-0 | 29-21-31 | D41972P | | | 11 | D40738P | | | 21 | ALL |
| 0505 | 20 | | GA | | 35-0 | 80-11-21 | D41972P | | | 15 | D40738P | | | 11 | ALL |
| 0515 | 24 | | GK | | 35-0 | SPARE | D41972P | | | 5 | D40738P | | | 15 | 115-199 |
| 0603 | 22 | | GA | | 42-0 | SPARE | D40624P | | | 3 | D41902P | | | 3 | 001-002, 115-199 |
| 0603 | 22 | | GA | | 43-0 | SPARE | D40624P | | | 3 | D41902P | | | 3 | 003-099 |
| 0604 | 22 | | GA | | 42-0 | SPARE | D40624P | | | 4 | D41902P | | | 4 | 001-002, 115-199 |
| 0604 | 22 | | GA | | 43-0 | SPARE | D40624P | | | 4 | D41902P | | | 4 | 003-099 |
| 0605 | 22 | | GA | | 42-0 | SPARE | D40624P | | | 5 | D41902P | | | 5 | 001-002, 115-199 |
| 0605 | 22 | | GA | | 43-0 | SPARE | D40624P | | | 5 | D41902P | | | 5 | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W2360

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2360 | 286N2360 | P11 TO E/E BAY - POWER DISTR-CAT S(B) (continued) | | | | | | | | | | | | | |
| 0606 | 22 | GA | 34-0 | SPARE | D40624P | 16 | | | D40738P | 10 | | | 115-199 | | |
| 0607 | 24 | GK | 34-0 | 36-11-31 | D40624P | 17 | | | D40738P | 4 | | | 001-002, 115-199 | | |
| 0607 | 24 | GK | 35-0 | 36-11-31 | D40624P | 17 | | | D40738P | 4 | | | 003-099 | | |
| 0608 | 22 | GA | 34-0 | SPARE | D40624P | 18 | | | D40738P | 7 | | | 115-199 | | |
| 0609 | 20 | GA | 34-0 | SPARE | D40624P | 19 | | | D40738P | 19 | | | 115-199 | | |
| 0611 | 22 | GA | 35-0 | SPARE | D41972P | 22 | | | D40738P | 22 | | | 115-199 | | |
| 0612 | 22 | GA | 35-0 | 23-32-02 | D41972P | 23 | | | D40738P | 23 | | | ALL | | |
| 0613 | 22 | GA | 35-0 | SPARE | D41972P | 24 | | | D40738P | 24 | | | 115-199 | | |
| 0614 | 22 | GA | 35-0 | SPARE | D41972P | 25 | | | D40738P | 25 | | | 115-199 | | |
| 0615 | 22 | GA | 35-0 | 77-12-42 | D41972P | 7 | | | D40738P | 5 | | | ALL | | |
| 0616 | 22 | GA | 27-0 | SPARE | D40624P | 6 | | | D40736P | 6 | | | 115-199 | | |
| 0617 | 22 | GA | 27-0 | SPARE | D40624P | 7 | | | D40736P | 7 | | | 115-199 | | |
| 0618 | 22 | GA | 27-0 | SPARE | D40624P | 8 | | | D40736P | 8 | | | 115-199 | | |
| 0619 | 22 | GA | 27-0 | SPARE | D40624P | 9 | | | D40736P | 9 | | | 115-199 | | |
| W2361 | 286N2361 | TOP TCAS ANTENNA | | | | | | | | | | | | | |
| 001CO | | AA | 0-0 | 34-45-02 | D41181P | =C1 | | | D41161J | =C1 | | | ALL | | |
| 001CX | 65 | AA | 19-3 | 34-45-02 | D41181P | =A1 | | | D41161J | =A1 | | | ALL | | |
| 002CO | | AB | 0-0 | 34-45-02 | D41185P | =C1 | | | D41163J | =C1 | | | ALL | | |
| 002CX | 65 | AB | 19-3 | 34-45-02 | D41185P | =A1 | | | D41163J | =A1 | | | ALL | | |
| 003CO | | AC | 0-0 | 34-45-02 | D41187P | =C1 | | | D41165J | =C1 | | | ALL | | |
| 003CX | 65 | AC | 19-3 | 34-45-02 | D41187P | =A1 | | | D41165J | =A1 | | | ALL | | |
| 004CO | | AD | 0-0 | 34-45-02 | D41189P | =C1 | | | D41167J | =C1 | | | ALL | | |
| 004CX | 65 | AD | 19-3 | 34-45-02 | D41189P | =A1 | | | D41167J | =A1 | | | ALL | | |
| W2362 | 286N2362 | P11 TO E/E BAY - POWER DISTR-CAT C | | | | | | | | | | | | | |
| 0001 | 20 | GA | 37-0 | 22-11-31 | D40626P | 1 | | | D41890P | 1 | | | 001-099 | | |
| 0001 | 20 | GA | 36-0 | 22-11-31 | D40626P | 1 | | | D41890P | 1 | | | 115-199 | | |
| 0002 | 20 | GA | 37-0 | SPARE | D40626P | 2 | | | D41890P | 2 | | | 001-099 | | |
| 0002 | 20 | GA | 36-0 | SPARE | D40626P | 2 | | | D41890P | 2 | | | 115-199 | | |
| 0003 | 20 | GA | 37-0 | 22-11-32 | D40626P | 3 | | | D41890P | 3 | | | 001-099 | | |
| 0003 | 20 | GA | 36-0 | 22-11-32 | D40626P | 3 | | | D41890P | 3 | | | 115-199 | | |
| 0004 | 22 | GA | 52-0 | 34-33-31 | D40626P | 4 | | | D41892P | 1 | | | 001-099 | | |
| 0004 | 22 | GA | 51-0 | 34-33-31 | D40626P | 4 | | | D41892P | 1 | | | 115-199 | | |
| 0005 | 20 | GA | 37-0 | 34-21-31 | D40626P | 5 | | | D41890P | 5 | | | 001-099 | | |
| 0005 | 20 | GA | 36-0 | 34-21-31 | D40626P | 5 | | | D41890P | 5 | | | 115-199 | | |
| 0006 | 24 | GK | 5-0 | 24-51-31 | D41892P | 3 | | | SP01094 | | 9 | | ALL | | |
| 0101 | 20 | GA | 36-0 | SPARE | D40626P | 11 | | | D41890P | 11 | | | 115-199 | | |
| 0102 | 20 | GA | 36-0 | SPARE | D40626P | 12 | | | D41890P | 12 | | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W2360

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2362 | 286N2362 | | | P11 TO E/E BAY - POWER DISTR-CAT C (continued) | | | | | | | | | | | |
| 0103 | 20 | | GA | | 36-0 | SPARE | D40626P | | 13 | | D41890P | | 13 | | 115-199 |
| 0104 | 20 | | GA | | 36-0 | SPARE | D40626P | | 14 | | D41890P | | 14 | | 115-199 |
| 0106 | 22 | | GA | | 52-0 | SPARE | D40626P | | 6 | | D41892P | | 6 | | 001-099 |
| 0106 | 22 | | GA | | 51-0 | SPARE | D40626P | | 6 | | D41892P | | 6 | | 115-199 |
| 0107 | 22 | | GA | | 51-0 | SPARE | D40626P | | 7 | | D41892P | | 7 | | 115-199 |
| 0108 | 22 | | GA | | 52-0 | SPARE | D40626P | | 8 | | D41892P | | 8 | | 001-099 |
| 0108 | 22 | | GA | | 51-0 | SPARE | D40626P | | 8 | | D41892P | | 8 | | 115-199 |
| 0109 | 22 | | GA | | 52-0 | 27-48-21 | D40626P | | 9 | | D41892P | | 9 | | 001-099 |
| 0109 | 22 | | GA | | 51-0 | 27-48-21 | D40626P | | 9 | | D41892P | | 9 | | 115-199 |
| W2363 | 286N2363 | | | TOP TCAS ANTENNA | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-45-02 | D41161P | | =C1 | | D01585 | | =C1 | | ALL |
| 001CX | | | | CW | 3-4 | 34-45-02 | D41161P | | =A1 | | D01585 | | =A1 | | ALL |
| 002CO | | | | AB | 0-0 | 34-45-02 | D41163P | | =C1 | | D01587 | | =C1 | | ALL |
| 002CX | | | | CW | 3-4 | 34-45-02 | D41163P | | =A1 | | D01587 | | =A1 | | ALL |
| 003CO | | | | AC | 0-0 | 34-45-02 | D41165P | | =C1 | | D01589 | | =C1 | | ALL |
| 003CX | | | | CW | 3-4 | 34-45-02 | D41165P | | =A1 | | D01589 | | =A1 | | ALL |
| 004CO | | | | AD | 0-0 | 34-45-02 | D41167P | | =C1 | | D01591 | | =C1 | | ALL |
| 004CX | | | | CW | 3-4 | 34-45-02 | D41167P | | =A1 | | D01591 | | =A1 | | ALL |
| W2364 | 286N2364 | | | P11 TO P1 - POWER DIST-CAT L | | | | | | | | | | | |
| 0001 | 22 | | GA | | 17-0 | 33-14-21 | D40748P | | 2 | | D40754J | | 1 | | 001-099 |
| 0001 | 22 | | GA | | 16-0 | 33-14-21 | D40748P | | 2 | | D40754J | | 1 | | 115-199 |
| 0002 | 24 | | GK | | 17-0 | SPARE | D40748P | | 1 | | D40754J | | 2 | | 001-099 |
| 0002 | 24 | | GK | | 16-0 | SPARE | D40748P | | 1 | | D40754J | | 2 | | 115-199 |
| 0003 | 22 | | GA | | 17-0 | SPARE | D40748P | | 11 | | D40754J | | 3 | | 001-099 |
| 0003 | 22 | | GA | | 17-0 | 34-13-11 | D40748P | | 11 | | D40754J | | 3 | | 010-099 |
| 0003 | 22 | | GA | | 16-0 | SPARE | D40748P | | 11 | | D40754J | | 3 | | 115-199 |
| 0004 | 24 | | GK | | 17-0 | 34-22-16 | D40748P | | 15 | | D40754J | | 4 | | 001-099 |
| 0004 | 24 | | GK | | 16-0 | 34-22-16 | D40748P | | 15 | | D40754J | | 4 | | 115-199 |
| 0006 | 22 | | GA | | 17-0 | 34-22-82 | D40748P | | 14 | | D40754J | | 6 | | 001-099 |
| 0006 | 22 | | GA | | 16-0 | 34-22-82 | D40748P | | 14 | | D40754J | | 6 | | 115-199 |
| 0007 | 24 | | GK | | 17-0 | 34-13-11 | D40748P | | 12 | | D40754J | | 7 | | 001-099 |
| 0007 | 24 | | GK | | 16-0 | 34-13-11 | D40748P | | 12 | | D40754J | | 7 | | 115-199 |
| 0008 | 24 | | GK | | 17-0 | 34-13-11 | D40748P | | 13 | | D40754J | | 8 | | 001-099 |
| 0008 | 24 | | GK | | 16-0 | 34-13-11 | D40748P | | 13 | | D40754J | | 8 | | 115-199 |
| 0009 | 22 | | GA | | 17-0 | 31-41-11 | D40748P | | 9 | | D40754J | | 9 | | 001-099 |
| 0009 | 22 | | GA | | 16-0 | 31-41-11 | D40748P | | 9 | | D40754J | | 9 | | 115-199 |
| 0010 | 24 | | GK | | 17-0 | 27-58-11 | D40748P | | 8 | | D40754J | | 10 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2360

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2364 | 286N2364 | | | | P11 TO P1 - POWER DIST-CAT L (continued) | | | | | | | | | | | |
| 0010 | 22 | | GA | | 16-0 | 27-58-11 | | D40748P | 8 | | | D40754J | 10 | | | 115-199 |
| 0011 | 22 | | GA | | 17-0 | SPARE | | D40748P | 7 | | | D40754J | 11 | | | 001-099 |
| 0011 | 22 | | GA | | 16-0 | SPARE | | D40748P | 7 | | | D40754J | 11 | | | 115-199 |
| 0014 | 24 | | GK | | 17-0 | 33-13-11 | | D40748P | 10 | | | D40754J | 14 | | | 001-099 |
| 0014 | 24 | | GK | | 16-0 | 33-13-11 | | D40748P | 10 | | | D40754J | 14 | | | 115-199 |
| 0016 | 16 | | GA | | 17-0 | 30-42-11 | | D40748P | 23 | | | D40754J | 23 | | | 001-099 |
| 0016 | 16 | | GA | | 16-0 | 30-42-11 | | D40748P | 23 | | | D40754J | 23 | | | 115-199 |
| 0017 | 22 | | GA | | 15-0 | 33-14-31 | | D40748P | 17 | | | SM00001 | | 9 | | 001-099 |
| 0017 | 22 | | GA | | 14-0 | 33-14-31 | | D40748P | 17 | | | SM00001 | | 9 | | 115-199 |
| 0018 | 24 | | GK | | 17-0 | 27-58-11 | | D40748P | 18 | | | D40754J | 18 | | | 001-099 |
| 0018 | 22 | | GA | | 16-0 | 27-58-11 | | D40748P | 18 | | | D40754J | 18 | | | 115-199 |
| 0027 | 22 | | GA | | 25-0 | 33-14-11 | | L00277 | =P | C | | D40754J | 21 | | | 115-199 |
| 0028 | 20 | | GA | | 8-0 | 33-14-11 | | L00277 | =G | C | | GD00601 | AC.. | 2 | | 115-199 |
| 0029 | 20 | | GA | | 8-0 | 33-14-31 | | TB5041 | 2 | D | | GD01017 | AC.. | 2 | | 001-099 |
| 0029 | 20 | | GA | | 6-0 | 33-14-31 | | TB5041 | 2 | D | | GD01017 | AC.. | 2 | | 115-199 |
| 0031 | 24 | | GK | | 17-0 | 34-22-16 | | D40748P | 19 | | | D40754J | 31 | | | 001-099 |
| 0031 | 24 | | GK | | 16-0 | 34-22-16 | | D40748P | 19 | | | D40754J | 31 | | | 115-199 |
| 0032 | 22 | | GA | | 4-0 | 33-14-31 | | TB5041 | 1 | D | | SM00001 | | 9 | | 001-099 |
| 0032 | 22 | | GA | | 3-0 | 33-14-31 | | TB5041 | 1 | D | | SM00001 | | 9 | | 115-199 |
| 0033 | 22 | | GA | | 13-0 | 33-14-31 | | TB5021 | 1 | D | | SM00001 | | 9 | | 001-099 |
| 0033 | 22 | | GA | | 12-0 | 33-14-31 | | TB5021 | 1 | D | | SM00001 | | 9 | | 115-199 |
| 0034 | 20 | | GA | | 7-0 | 33-14-31 | | TB5021 | 2 | D | | GD00343 | AC.. | 2 | | 001-099 |
| 0034 | 20 | | GA | | 8-0 | 33-14-31 | | TB5021 | 2 | D | | GD00343 | AC.. | 2 | | 115-199 |
| 0602 | 22 | | GA | | 17-0 | 34-61-15 | | D40748P | 22 | | | D40754J | 22 | | | 001-099 |
| 0603 | 22 | | GA | | 17-0 | SPARE | | D40748P | 24 | | | D40754J | 24 | | | 001-099 |
| 0603 | 22 | | GA | | 16-0 | SPARE | | D40748P | 24 | | | D40754J | 24 | | | 115-199 |
| 0605 | 22 | | GA | | 16-0 | SPARE | | D40748P | 25 | | | D40754J | 25 | | | 115-199 |
| 0606 | 22 | | GA | | 16-0 | SPARE | | D40748P | 26 | | | D40754J | 26 | | | 115-199 |
| 0607 | 22 | | GA | | 16-0 | SPARE | | D40748P | 27 | | | D40754J | 27 | | | 115-199 |
| 0608 | 22 | | GA | | 16-0 | SPARE | | D40748P | 28 | | | D40754J | 28 | | | 115-199 |
| A-A | | | | | 0-0 | 33-14-31 | | TB5041 | 1 | D | | L00375 | =P | | | ALL |
| A-B | | | | | 0-0 | 33-14-31 | | TB5041 | 2 | D | | L00375 | =G | | | ALL |
| A-C | | | | | 0-0 | 33-14-31 | | TB5021 | 1 | D | | L00575 | =P | | | ALL |
| A-D | | | | | 0-0 | 33-14-31 | | TB5021 | 2 | D | | L00575 | =G | | | ALL |
| W2365 | 286N2365 | | | | BOTTOM TCAS ANTENNA | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-45-02 | | D41191P | =C1 | | | D41171J | =C1 | | | ALL |
| 001CX | | | 17 | AA | 7-2 | 34-45-02 | | D41191P | =A1 | | | D41171J | =A1 | | | ALL |
| 002CO | | | | AB | 0-0 | 34-45-02 | | D41193P | =C1 | | | D41173J | =C1 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2360

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|----------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2365 | 286N2365 | | | | BOTTOM TCAS ANTENNA (continued) | | | | | | | | | | | | |
| 002CX | | | 17 | AB | 7-2 | 34-45-02 | D41193P | = | A1 | | | D41173J | = | A1 | | ALL | |
| 003CO | | | | AC | 0-0 | 34-45-02 | D41195P | = | C1 | | | D41177J | = | C1 | | ALL | |
| 003CX | | | 17 | AC | 7-2 | 34-45-02 | D41195P | = | A1 | | | D41177J | = | A1 | | ALL | |
| 004CO | | | | AD | 0-0 | 34-45-02 | D41197P | = | C1 | | | D41179J | = | C1 | | ALL | |
| 004CX | | | 17 | AD | 7-1 | 34-45-02 | D41197P | = | A1 | | | D41179J | = | A1 | | ALL | |
| W2366 | 286N2366 | | | | P11 TO P3 - POWER DISTR - CAT. R | | | | | | | | | | | | |
| 0001 | 24 | | GK | | 18-0 | 33-13-41 | D40750P | | 1 | | | D40756J | | 1 | | 001-099 | |
| 0001 | 24 | | GK | | 22-0 | 33-13-41 | D40750P | | 1 | | | D40756J | | 1 | | 115-199 | |
| 0002 | 24 | | GK | | 18-0 | 34-22-91 | D40750P | | 2 | | | D40756J | | 2 | | 001-099 | |
| 0002 | 24 | | GK | | 22-0 | SPARE | D40750P | | 2 | | | D40756J | | 2 | | 115-199 | |
| 0003 | 24 | | GK | | 18-0 | 34-22-26 | D40750P | | 3 | | | D40756J | | 3 | | 001-099 | |
| 0003 | 24 | | GK | | 22-0 | 34-22-26 | D40750P | | 3 | | | D40756J | | 3 | | 115-199 | |
| 0004 | 24 | | GK | | 18-0 | 34-22-26 | D40750P | | 4 | | | D40756J | | 4 | | 001-099 | |
| 0004 | 24 | | GK | | 22-0 | 34-22-26 | D40750P | | 4 | | | D40756J | | 4 | | 115-199 | |
| 0005 | 22 | | GA | | 18-0 | 34-22-92 | D40750P | | 5 | | | D40756J | | 5 | | 001-099 | |
| 0005 | 22 | | GA | | 22-0 | 34-22-92 | D40750P | | 5 | | | D40756J | | 5 | | 115-199 | |
| 0006 | 22 | | GA | | 18-0 | 33-14-11 | D40750P | | 14 | | | D40756J | | 6 | | 001-099 | |
| 0006 | 22 | | GA | | 22-0 | 33-14-11 | D40750P | | 14 | | | D40756J | | 6 | | 115-199 | |
| 0007 | 22 | | GA | | 18-0 | 31-25-11 | D40750P | | 6 | | | D40756J | | 7 | | 001-099 | |
| 0007 | 22 | | GA | | 22-0 | 31-25-11 | D40750P | | 6 | | | D40756J | | 7 | | 115-199 | |
| 0008 | 20 | | GA | | 22-0 | 32-42-12 | D40750P | | 7 | | | D40756J | | 8 | | 115-199 | |
| 0009 | 22 | | GA | | 18-0 | 34-61-25 | D40750P | | 9 | | | D40756J | | 9 | | 001-099 | |
| 0010 | 24 | | GK | | 18-0 | 33-13-21 | D40750P | | 11 | | | D40756J | | 10 | | 001-099 | |
| 0010 | 24 | | GK | | 22-0 | 33-13-21 | D40750P | | 11 | | | D40756J | | 10 | | 115-199 | |
| 0011 | 24 | | GK | | 18-0 | 34-13-21 | D40750P | | 17 | | | D40756J | | 11 | | 001-099 | |
| 0011 | 24 | | GK | | 22-0 | 34-13-21 | D40750P | | 17 | | | D40756J | | 11 | | 115-199 | |
| 0012 | 24 | | GK | | 18-0 | 34-13-21 | D40750P | | 16 | | | D40756J | | 12 | | 001-099 | |
| 0012 | 24 | | GK | | 22-0 | 34-13-21 | D40750P | | 16 | | | D40756J | | 12 | | 115-199 | |
| 0013 | 22 | | GA | | 18-0 | 32-31-11 | D40750P | | 13 | | | D40756J | | 13 | | 001-099 | |
| 0013 | 22 | | GA | | 22-0 | 32-31-11 | D40750P | | 13 | | | D40756J | | 13 | | 115-199 | |
| 0014 | 22 | | GA | | 26-0 | 33-14-11 | D40756J | | 14 | | | L00278 | = | P | C | 115-199 | |
| 0015 | 22 | | GA | | 2-0 | 33-14-31 | D40750P | | 15 | | | SM00001 | | 9 | | 001-099 | |
| 0015 | 22 | | GA | | 1-0 | 33-14-31 | D40750P | | 15 | | | SM00001 | | 9 | | 115-199 | |
| 0016 | 22 | | GA | | 21-0 | 31-41-21 | D40750P | | 8 | | | TB0016X | D001 | BJ | | 001-099 | |
| 0016 | 22 | | GA | | 25-0 | 31-41-21 | D40750P | | 8 | | | TB0016X | D001 | BJ | | 115-199 | |
| 0019 | 20 | | GA | | 18-0 | SPARE | D40750P | | 19 | | | D40756J | | 15 | | 001-099 | |
| 0019 | 20 | | GA | | 22-0 | SPARE | D40750P | | 19 | | | D40756J | | 15 | | 115-199 | |
| 0020 | 22 | | GA | | 18-0 | SPARE | D40750P | | 20 | | | D40756J | | 16 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2360

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2366 | 286N2366 | | | P11 TO P3 - POWER DISTR - CAT. R (continued) | | | | | | | | | | | |
| 0020 | 20 | | GA | | 22-0 | SPARE | D40750P | 20 | | | D40756J | 16 | | | 115-199 |
| 0021 | 20 | | GA | | 22-0 | SPARE | D40750P | 21 | | | D40756J | 21 | | | 115-199 |
| 0022 | 20 | | GA | | 18-0 | 29-21-32 | D40750P | 22 | | | D40756J | 18 | | | 001-099 |
| 0022 | 20 | | GA | | 22-0 | 29-21-32 | D40750P | 22 | | | D40756J | 18 | | | 115-199 |
| 0023 | 20 | | GA | | 18-0 | 29-21-32 | D40750P | 25 | | | D40756J | 19 | | | 001-099 |
| 0023 | 20 | | GA | | 22-0 | 29-21-32 | D40750P | 25 | | | D40756J | 19 | | | 115-199 |
| 0024 | 20 | | GA | | 22-0 | SPARE | D40750P | 24 | | | D40756J | 20 | | | 115-199 |
| 0027 | 20 | | GA | | 5-0 | 33-14-11 | L00278 | =G | C | | GD00608 | AC.. | 2 | | 115-199 |
| 0028 | 20 | | GA | | 4-0 | 33-14-31 | TB5042 | 2 | D | | GD01252 | AC.. | 2 | | 001-099 |
| 0028 | 20 | | GA | | 5-0 | 33-14-31 | TB5042 | 2 | D | | GD01252 | AC.. | 2 | | 115-199 |
| 0029 | 22 | | GA | | 17-0 | 33-14-31 | TB5042 | 1 | D | | SM00001 | | 9 | | 001-099 |
| 0029 | 22 | | GA | | 21-0 | 33-14-31 | TB5042 | 1 | D | | SM00001 | | 9 | | 115-199 |
| 0030 | 22 | | GA | | 10-0 | 33-14-31 | SM00001 | | 9 | | TB5043 | 1 | D | | 001-099 |
| 0030 | 22 | | GA | | 4-6 | 33-14-31 | SM00001 | | 9 | | TB5043 | 1 | D | | 115-199 |
| 0031 | 20 | | GA | | 5-0 | 33-14-31 | TB5043 | 2 | D | | GD00619 | AC.. | 2 | | 001-099 |
| 0031 | 20 | | GA | | 6-0 | 33-14-31 | TB5043 | 2 | D | | GD00619 | AC.. | 2 | | 115-199 |
| 0032 | 16 | | GA | | 18-0 | 30-42-11 | D40750P | 23 | | | D40756J | 23 | | | 001-099 |
| 0032 | 16 | | GA | | 22-0 | 30-42-11 | D40750P | 23 | | | D40756J | 23 | | | 115-199 |
| 0127 | 22 | | GA | | 18-0 | SPARE | D40750P | 27 | | | D40756J | 27 | | | 001-099 |
| 0127 | 22 | | GA | | 21-0 | SPARE | D40750P | 27 | | | D40756J | 27 | | | 115-199 |
| A-A | | | | | 0-0 | 33-14-31 | L00376 | =P | | | TB5042 | 1 | D | | ALL |
| A-B | | | | | 0-0 | 33-14-31 | L00376 | =G | | | TB5042 | 2 | D | | ALL |
| A-C | | | | | 0-0 | 33-14-31 | L00377 | =P | | | TB5043 | 1 | D | | ALL |
| A-D | | | | | 0-0 | 33-14-31 | L00377 | =G | | | TB5043 | 2 | D | | ALL |
| B-A | | | | | 0-0 | 33-11-21 | L00444 | W-A | | | SP01464 | | 9 | | 115-199 |
| B-B | | | | | 0-0 | 33-11-21 | L00444 | W-B | | | GD00604 | DC.. | 2 | | 115-199 |
| C-A | | | | | 0-0 | 33-11-21 | L00443 | W-A | | | SP01464 | | 9 | | 115-199 |
| C-B | | | | | 0-0 | 33-11-21 | L00443 | W-B | | | GD00600 | DC.. | 2 | | 115-199 |
| W2367 | 286N2367 | | | BOTTOM TCAS ANTENNA | | | | | | | | | | | |
| 001CO | | | AA | | 0-0 | 34-45-02 | D41171P | =C1 | | | D01593 | =C1 | | | ALL |
| 001CX | | 17 | AA | | 3-0 | 34-45-02 | D41171P | =A1 | | | D01593 | =A1 | | | ALL |
| 002CO | | | AB | | 0-0 | 34-45-02 | D41173P | =C1 | | | D01595 | =C1 | | | ALL |
| 002CX | | 17 | AB | | 3-0 | 34-45-02 | D41173P | =A1 | | | D01595 | =A1 | | | ALL |
| 003CO | | | AC | | 0-0 | 34-45-02 | D41177P | =C1 | | | D01597 | =C1 | | | ALL |
| 003CX | | 17 | AC | | 3-0 | 34-45-02 | D41177P | =A1 | | | D01597 | =A1 | | | ALL |
| 004CO | | | AD | | 0-0 | 34-45-02 | D41179P | =C1 | | | D01599 | =C1 | | | ALL |
| 004CX | | 17 | AD | | 3-0 | 34-45-02 | D41179P | =A1 | | | D01599 | =A1 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2360

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | FT-IN | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2368 | 286N2368 | | | P11 TO P1 POWER DIST-CAT. S | | | | | | | | | | | |
| 0001 | 24 | | GK | 16-0 | 34-22-81 | D40752P | | 1 | | | D40758J | 1 | | | 001-099 |
| 0001 | 24 | | GK | 16-0 | 34-22-83 | D40752P | | 1 | | | D40758J | 1 | | | 115-199 |
| 0002 | 24 | | GK | 16-0 | 34-13-11 | D40752P | | 2 | | | D40758J | 2 | | | ALL |
| 0003 | 24 | | GK | 16-0 | 33-13-12 | D40752P | | 3 | | | D40758J | 3 | | | ALL |
| 0004 | 24 | | GK | 16-0 | 77-12-11 | D40752P | | 4 | | | D40758J | 4 | | | ALL |
| 0005 | 22 | | GA | 16-0 | 34-12-61 | D40752P | | 5 | | | D40758J | 5 | | | ALL |
| 0006 | 22 | | GA | 16-0 | 34-12-62 | D40752P | | 6 | | | D40758J | 6 | | | ALL |
| 0007 | 20 | | GA | 13-0 | 33-13-11 | SP01056 | | | 9 | | D40758J | 9 | | | ALL |
| 0008 | 22 | | GA | 16-0 | 31-25-11 | D40752P | | 7 | | | D40758J | 10 | | | 001-099 |
| 0607 | 22 | | GA | 16-0 | SPARE | D40752P | | 7 | | | D40758J | 7 | | | 115-199 |
| 0608 | 22 | | GA | 16-0 | SPARE | D40752P | | 8 | | | D40758J | 8 | | | 115-199 |
| 0610 | 22 | | GA | 16-0 | 31-25-11 | D40752P | | 10 | | | D40758J | 10 | | | 115-199 |
| 0611 | 22 | | GA | 16-0 | SPARE | D40752P | | 11 | | | D40758J | 11 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2360

Page 7 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|----|---------------------------------------|------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2370 | 286N2370 | | | P6 TO E/E AREA - CENTER BUS | | | | | | | | | | | |
| 0001 | 22 | | GA | | 30-0 | 22-11-32 | D40300P | | 1 | | D41888P | | 1 | | ALL |
| 0002 | 22 | | GA | | 30-0 | 22-11-32 | D40300P | | 2 | | D41888P | | 2 | | ALL |
| 0004 | 24 | | GK | | 32-0 | 24-51-31 | D40300P | | 4 | | D41320P | | 4 | | 001-099 |
| 0004 | 24 | | GK | | 31-0 | 24-51-31 | D40300P | | 4 | | D41320P | | 4 | | 115-199 |
| 0005 | 24 | | GK | | 32-0 | 24-51-31 | D40300P | | 5 | | D41320P | | 5 | | 001-099 |
| 0005 | 24 | | GK | | 31-0 | 24-51-31 | D40300P | | 5 | | D41320P | | 5 | | 115-199 |
| 0006 | 24 | | GK | | 35-0 | 24-51-31 | D40300P | | 3 | | SP01094 | | 9 | | ALL |
| 0101 | 22 | | GA | | 32-0 | SPARE | D40300P | | 7 | | D41320P | | 6 | | 001-099 |
| 0101 | 22 | | GA | | 31-0 | SPARE | D40300P | | 7 | | D41320P | | 6 | | 115-199 |
| 0102 | 22 | | GA | | 32-0 | SPARE | D40300P | | 8 | | D41320P | | 7 | | 001-099 |
| 0102 | 22 | | GA | | 31-0 | SPARE | D40300P | | 8 | | D41320P | | 7 | | 115-199 |
| 0103 | 22 | | GA | | 31-0 | SPARE | D40300P | | 9 | | D41320P | | 8 | | 115-199 |
| 0104 | 22 | | GA | | 30-0 | SPARE | D40300P | | 10 | | D41888P | | 3 | | 115-199 |
| 0105 | 22 | | GA | | 30-0 | SPARE | D40300P | | 11 | | D41888P | | 4 | | 115-199 |
| W2379 | 286N2379 | | | WEATHER RADAR INTERFACE - LEFT | | | | | | | | | | | |
| 0001 | 22 | | CQ | | 14-0 | 34-46-14 | D65001J | | 1 | | D23005P | | 1 | | 002 |
| 0002 | 22 | | CQ | | 17-0 | 34-46-14 | D65001J | | 5 | | SP02226 | | 9 | | 002 |
| 0003 | 22 | | CQ | | 14-0 | 34-46-14 | D65001J | | 4 | | D23005P | | 5 | | 002 |
| 0021 | 22 | | CQ | | 14-0 | 34-22-18 | D65001J | | 39 | | D23005P | | 22 | | 002 |
| 0022 | 22 | | CQ | | 14-0 | 34-22-18 | D65001J | | 46 | | D23005P | | 23 | | 002 |
| 2001B | 24 | | 7K | AA | 14-0 | 34-46-14 | D65001J | | 3 | | D23005P | | 3 | | 002 |
| 2001W | 24 | | 7K | AA | 0-0 | 34-46-14 | D65001J | | 2 | | D23005P | | 2 | | 002 |
| 2001Z | | | | AA | 0-0 | 34-46-14 | D65001J | | 9 | | D23005P | | 4 | | 002 |
| 2003B | 24 | | 7K | AB | 14-0 | 34-43-15 | D65001J | | 11 | | D21001P | | 2 | | 002 |
| 2003W | 24 | | 7K | AB | 0-0 | 34-43-15 | D65001J | | 10 | | D21001P | | 1 | | 002 |
| 2003Z | | | | AB | 0-0 | 34-43-15 | D65001J | | 12 | | D21001P | | 3 | | 002 |
| 2005B | 24 | | 7K | AD | 14-0 | 34-43-15 | D65001J | | 21 | | D21001P | | 8 | | 002 |
| 2005W | 24 | | 7K | AD | 0-0 | 34-43-15 | D65001J | | 20 | | D21001P | | 7 | | 002 |
| 2005Z | | | | AD | 0-0 | 34-43-15 | D65001J | | 19 | | D21001P | | 9 | | 002 |
| 2006B | 24 | | 7K | AE | 14-0 | 34-43-15 | D65001J | | 24 | | D23005P | | 7 | | 002 |
| 2006W | 24 | | 7K | AE | 0-0 | 34-43-15 | D65001J | | 23 | | D23005P | | 6 | | 002 |
| 2006Z | | | | AE | 0-0 | 34-43-15 | D65001J | | 22 | | D23005P | | 8 | | 002 |
| 2008B | 22 | | GU | AH | 14-0 | 34-46-14 | D65001J | | 26 | | D23005P | | 14 | | 002 |
| 2008R | 22 | | GU | AH | 0-0 | 34-46-14 | D65001J | | 25 | | D23005P | | 13 | | 002 |
| 2008Z | | | | AH | 0-0 | 34-46-14 | D65001J | | 27 | | D23005P | | 15 | | 002 |
| 2009B | 22 | | GU | AI | 14-0 | 34-43-11 | D65001J | | 30 | | D21001P | | 17 | | 002 |
| 2009R | 22 | | GU | AI | 0-0 | 34-43-11 | D65001J | | 29 | | D21001P | | 16 | | 002 |
| 2009Z | | | | AI | 0-0 | 34-43-11 | D65001J | | 28 | | D21001P | | 18 | | 002 |

WIRE LIST

D280N032

91-21-11

Section W2370

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2379 | 286N2379 | | | WEATHER RADAR INTERFACE - LEFT (continued) | | | | | | | | | | | |
| 2501B | 22 | GU | AL | | 14-0 | 34-22-18 | D65001J | 37 | | | D21001P | 28 | | | 002 |
| 2501R | 22 | GU | AL | | 0-0 | 34-22-18 | D65001J | 36 | | | D21001P | 27 | | | 002 |
| 2501Z | | | AL | | 0-0 | 34-22-18 | D65001J | 38 | | | D21001P | 29 | | | 002 |
| 2502B | 22 | GU | AM | | 14-0 | 34-22-18 | D65001J | 44 | | | D23005P | 20 | | | 002 |
| 2502R | 22 | GU | AM | | 0-0 | 34-22-18 | D65001J | 43 | | | D23005P | 19 | | | 002 |
| 2502Z | | | AM | | 0-0 | 34-22-18 | D65001J | 45 | | | D23005P | 21 | | | 002 |

WIRE LIST
D280N032

91-21-11
Section W2370
Page 2 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | Effectivity | | | |
|------------|-------------|----|-------|---------------------------------|------|----------|---------|-------|------|------|---------|-------------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | | Equip | Term | Type |
| W2381 | 286N2381 | | | WEATHER RADAR INTERFACE - RIGHT | | | | | | | | | | | |
| 0001 | 22 | CQ | | | 14-0 | 34-46-14 | D65003J | 1 | | | D23003P | 7 | | | 002 |
| 0002 | 22 | CQ | | | 14-0 | 34-46-14 | D65003J | 2 | | | D23003P | 8 | | | 002 |
| 0023 | 22 | CQ | | | 14-0 | 34-22-28 | D65003J | 39 | | | D23003P | 22 | | | 002 |
| 0024 | 22 | CQ | | | 14-0 | 34-22-28 | D65003J | 46 | | | D23003P | 23 | | | 002 |
| 2001B | 24 | 7K | AB | | 14-0 | 34-43-15 | D65003J | 8 | | | D23003P | 6 | | | 002 |
| 2001W | 24 | 7K | AB | | 0-0 | 34-43-15 | D65003J | 7 | | | D23003P | 5 | | | 002 |
| 2001Z | | | AB | | 0-0 | 34-43-15 | D65003J | 6 | | | D23003P | 4 | | | 002 |
| 2002B | 24 | 7K | AC | | 14-0 | 34-43-15 | D65003J | 11 | | | D22001P | 2 | | | 002 |
| 2002W | 24 | 7K | AC | | 0-0 | 34-43-15 | D65003J | 10 | | | D22001P | 1 | | | 002 |
| 2002Z | | | AC | | 0-0 | 34-43-15 | D65003J | 9 | | | D22001P | 3 | | | 002 |
| 2005B | 24 | 7K | AA | | 14-0 | 34-46-14 | D65003J | 4 | | | D23003P | 10 | | | 002 |
| 2005W | 24 | 7K | AA | | 0-0 | 34-46-14 | D65003J | 3 | | | D23003P | 9 | | | 002 |
| 2005Z | | | AA | | 0-0 | 34-46-14 | D65003J | 5 | | | D23003P | 11 | | | 002 |
| 2008B | 22 | GU | AH | | 14-0 | 34-46-14 | D65003J | 26 | | | D23003P | 13 | | | 002 |
| 2008R | 22 | GU | AH | | 0-0 | 34-46-14 | D65003J | 25 | | | D23003P | 12 | | | 002 |
| 2008Z | | | AH | | 0-0 | 34-46-14 | D65003J | 24 | | | D23003P | 14 | | | 002 |
| 2009B | 22 | GU | AI | | 14-0 | 34-43-11 | D65003J | 32 | | | D22001P | 14 | | | 002 |
| 2009R | 22 | GU | AI | | 0-0 | 34-43-11 | D65003J | 31 | | | D22001P | 13 | | | 002 |
| 2009Z | | | AI | | 0-0 | 34-43-11 | D65003J | 30 | | | D22001P | 15 | | | 002 |
| 2012B | 24 | 7K | AN | | 14-0 | 34-43-15 | D65003J | 33 | | | D22001P | 5 | | | 002 |
| 2012W | 24 | 7K | AN | | 0-0 | 34-43-15 | D65003J | 34 | | | D22001P | 4 | | | 002 |
| 2012Z | | | AN | | 0-0 | 34-43-15 | D65003J | 35 | | | D22001P | 6 | | | 002 |
| 2503B | 22 | GU | AL | | 14-0 | 34-22-28 | D65003J | 37 | | | D22001P | 23 | | | 002 |
| 2503R | 22 | GU | AL | | 0-0 | 34-22-28 | D65003J | 36 | | | D22001P | 22 | | | 002 |
| 2503Z | | | AL | | 0-0 | 34-22-28 | D65003J | 38 | | | D22001P | 24 | | | 002 |
| 2504B | 22 | GU | AM | | 14-0 | 34-22-28 | D65003J | 44 | | | D23003P | 20 | | | 002 |
| 2504R | 22 | GU | AM | | 0-0 | 34-22-28 | D65003J | 43 | | | D23003P | 19 | | | 002 |
| 2504Z | | | AM | | 0-0 | 34-22-28 | D65003J | 45 | | | D23003P | 21 | | | 002 |
| W2382 | 286N2382 | | | E1-1 TO P6 | | | | | | | | | | | |
| 0001 | 08 | HA | | | 27-9 | 24-31-11 | TB5019 | 12 | E | | TB0012 | 1 | E | | 003-099 |
| W2384 | 286N2384 | | | E1-2 TO LEFT WINDOW 1 | | | | | | | | | | | |
| 0001 | 20 | GA | | | 3-0 | 30-41-11 | TB5028 | 7 | E | | GD01016 | ST.. | 2 | | 001-099 |
| 0001 | 20 | GA | | | 4-0 | 30-41-11 | TB5028 | 7 | E | | GD01016 | ST.. | 2 | | 115-199 |
| 2001B | 12 | GB | AA | | 33-0 | 30-41-11 | D41592P | 1 | | | TB5028 | 1 | E | | ALL |
| 2001R | 12 | GB | AA | | 0-0 | 30-41-11 | D41592P | 2 | | | TB5028 | 2 | E | | ALL |
| 2501B | 22 | GU | AB | | 33-0 | 30-41-11 | D41594P | 2 | | | TB5028 | 3 | E | | ALL |
| 2501R | 22 | GU | AB | | 0-0 | 30-41-11 | D41594P | 3 | | | TB5028 | 4 | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2380

Page 1

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2380
Page 2
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|---|-------|----------|----------|---------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2386 | 286N2386 | E1-1 TO L WINDOW 2 AND 3 (continued) | | | | | | | | | | | | | |
| FRAD | | | 0-0 | 30-41-12 | TB5030 | 7 | C | | TB5030 | | | AD | 115-199 | | |
| W2388 | 286N2388 | E1-2 TO RIGHT WINDOW 2 AND 3 | | | | | | | | | | | | | |
| 0001 | 20 | GA | 34-0 | 30-41-11 | D41596P | 1 | | | SM00001 | 9 | | | 001-099 | | |
| 0001 | 20 | GA | 39-0 | 30-41-11 | D41596P | 1 | | | SM00001 | 9 | | | 115-199 | | |
| 0002 | 20 | GA | 17-0 | 30-41-11 | GD00979 | AC.. | E | | SM00002 | 9 | | | 001-099 | | |
| 0002 | 20 | GA | 22-0 | 30-41-11 | GD00979 | AC.. | E | | SM00002 | 9 | | | 115-199 | | |
| 0003 | 20 | GA | 17-0 | 30-41-11 | GD00977 | ST.. | E | | SM00003 | | | AF | 001-099 | | |
| 0003 | 20 | GA | 22-0 | 30-41-11 | GD00977 | ST.. | E | | SM00006 | | | AF | 115-199 | | |
| 0004 | 20 | GA | 29-0 | 30-41-11 | D41596P | 7 | | | TB5040 | 1 | C | | ALL | | |
| 0005 | 20 | GA | 2-0 | 30-41-11 | GD00979 | AC.. | E | | TB5040 | 2 | C | | 001-099 | | |
| 0005 | 20 | GA | 3-0 | 30-41-11 | GD00979 | AC.. | E | | TB5040 | 2 | C | | 115-199 | | |
| 0006 | 20 | GA | 2-0 | 30-41-11 | GD00977 | ST.. | E | | TB5040 | 7 | C | | 001-099 | | |
| 0006 | 20 | GA | 3-0 | 30-41-11 | GD00977 | ST.. | E | | TB5040 | 7 | C | | 115-199 | | |
| 2501B | 22 | GU | AA | 39-0 | 30-41-11 | D41596P | 2 | | SM00005 | 9 | | | 115-199 | | |
| 2501R | 22 | GU | AA | 0-0 | 30-41-11 | D41596P | 3 | | SM00006 | 9 | | | 115-199 | | |
| 2501Z | | | AA | 0-0 | 30-41-11 | D41596P | | AA | SM00006 | | | AF | 115-199 | | |
| 2502B | 22 | GU | AB | 34-0 | 30-41-11 | D41596P | 4 | | SM00003 | 9 | | | 001-099 | | |
| 2502B | 22 | GU | AB | 39-0 | 30-41-11 | D41596P | 4 | | SM00003 | 9 | | | 115-199 | | |
| 2502R | 22 | GU | AB | 0-0 | 30-41-11 | D41596P | 5 | | SM00004 | 9 | | | ALL | | |
| 2502Z | | | AB | 0-0 | 30-41-11 | D41596P | 6 | | SM00003 | | | AF | 001-099 | | |
| 2502Z | | | AB | 0-0 | 30-41-11 | D41596P | | AA | SM00006 | | | AF | 115-199 | | |
| 2503B | 22 | GU | AC | 29-6 | 30-41-11 | D41596P | 8 | | TB5040 | 3 | C | | ALL | | |
| 2503R | 22 | GU | AC | 0-0 | 30-41-11 | D41596P | 9 | | TB5040 | 4 | C | | ALL | | |
| 2503Z | | | AC | 0-0 | 30-41-11 | D41596P | 12 | | TB5040 | 7 | C | | 001-099 | | |
| 2503Z | | | AC | 0-0 | 30-41-11 | D41596P | | AB | TB5040 | | | AD | 115-199 | | |
| 2504B | 22 | GU | AD | 29-6 | 30-41-11 | D41596P | 10 | | TB5040 | 5 | C | | 115-199 | | |
| 2504R | 22 | GU | AD | 0-0 | 30-41-11 | D41596P | 11 | | TB5040 | 6 | C | | 115-199 | | |
| 2504Z | | | AD | 0-0 | 30-41-11 | D41596P | | AB | TB5040 | | | AD | 115-199 | | |
| 4501G | 22 | 8U | AE | 4-0 | 30-41-11 | SM00004 | CAP | Y | D41576P | 5 | | | 001-099 | | |
| 4501G | 22 | 8U | AE | 4-0 | 30-41-11 | SM00006 | | 9 | D41576P | 5 | | | 115-199 | | |
| 4501K | 20 | 8U | AE | 0-0 | 30-41-11 | SM00001 | | 9 | D41576P | 1 | | | ALL | | |
| 4501N | 22 | 8U | AE | 0-0 | 30-41-11 | SM00004 | | 9 | D41576P | 3 | | | ALL | | |
| 4501O | 20 | 8U | AE | 0-0 | 30-41-11 | SM00002 | | 9 | D41576P | 6 | | | ALL | | |
| 4501R | 22 | 8U | AE | 0-0 | 30-41-11 | SM00003 | | 9 | D41576P | 2 | | | ALL | | |
| 4501Y | 22 | 8U | AE | 0-0 | 30-41-11 | SM00004 | CAP | Y | D41576P | 4 | | | 001-099 | | |
| 4501Y | 22 | 8U | AE | 0-0 | 30-41-11 | SM00005 | | 9 | D41576P | 4 | | | 115-199 | | |
| FRAA | | | | 0-0 | 30-41-11 | D41596P | 6 | | D41596P | | | AA | 115-199 | | |
| FRAB | | | | 0-0 | 30-41-11 | D41596P | 12 | | D41596P | | | AB | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W2380

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2388 | 286N2388 | | | E1-2 TO RIGHT WINDOW 2 AND 3 (continued) | | | | | | | | | | | |
| FRAD | | | | | 0-0 | 30-41-11 | TB5040 | 7 | C | | TB5040 | | | AD | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W2380
Page 4 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|-------------|--|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2390 | 286N2390 | | | | E1-1 TO R WINDOW 1 | | | | | | | | | | |
| 0001 | 20 | | GA | | 3-0 | 30-41-12 | TB5038 | 7 | E | | GD01247 | ST.. | 2 | | 001-099 |
| 0001 | 20 | | GA | | 5-0 | 30-41-12 | TB5038 | 7 | E | | GD01247 | ST.. | 2 | | 115-199 |
| 2001B | 12 | | GB | AA | 32-0 | 30-41-12 | D41602P | 1 | | | TB5038 | 1 | E | | 001-099 |
| 2001B | 12 | | GB | AA | 33-0 | 30-41-12 | D41602P | 1 | | | TB5038 | 1 | E | | 115-199 |
| 2001R | 12 | | GB | AA | 0-0 | 30-41-12 | D41602P | 2 | | | TB5038 | 2 | E | | ALL |
| 2501B | 22 | | GU | AB | 31-0 | 30-41-12 | D41604P | 2 | | | TB5038 | 3 | E | | 001-099 |
| 2501B | 22 | | GU | AB | 33-0 | 30-41-12 | D41604P | 2 | | | TB5038 | 3 | E | | 115-199 |
| 2501R | 22 | | GU | AB | 0-0 | 30-41-12 | D41604P | 3 | | | TB5038 | 4 | E | | ALL |
| 2501Z | | | | AB | 0-0 | 30-41-12 | D41604P | 6 | | | TB5038 | 7 | E | | 001-099 |
| 2501Z | | | | AB | 0-0 | 30-41-12 | D41604P | | | AA | TB5038 | | | AB | 115-199 |
| 2502B | 22 | | GU | AC | 33-0 | 30-41-12 | D41604P | 4 | | | TB5038 | 5 | E | | 115-199 |
| 2502R | 22 | | GU | AC | 0-0 | 30-41-12 | D41604P | 5 | | | TB5038 | 6 | E | | 115-199 |
| 2502Z | | | | AC | 0-0 | 30-41-12 | D41604P | | | AA | TB5038 | | | AB | 115-199 |
| FRAA | | | | | 0-0 | 30-41-12 | D41604P | 6 | | | D41604P | | | AA | 115-199 |
| FRAB | | | | | 0-0 | 30-41-12 | TB5038 | 7 | E | | TB5038 | | | AB | 115-199 |
| W2392 | 286N2392 | | | | HYDRAULIC GENERATOR DC POWER FEEDER | | | | | | | | | | |
| 0001 | 06 | | CQ | | 34-0 | 24-31-11 | TB5019 | 12 | E | | K10564 | A2 | F | | 001-002, 115-199 |
| W2394 | 286N2394 | | | | P71 TO HYDRAULIC MOTOR GENERATOR (H) | | | | | | | | | | |
| 0001 | 12 | | HA | | 71-0 | 24-25-12 | D40418P | 1 | | | D07068 | 1 | | | ALL |
| 0002 | 12 | | HA | | 71-0 | 24-25-12 | D40418P | 2 | | | D07068 | 2 | | | ALL |
| 0003 | 12 | | HA | | 71-0 | 24-25-12 | D40418P | 3 | | | D07068 | 3 | | | ALL |
| 0004 | 12 | | HA | | 2-0 | 24-25-12 | D07068 | 4 | | | GD03156 | AC.. | E | | ALL |
| W2396 | 286N2396 | | | | P71 TO HYD MOTOR GEN AND GEN SHUT OFF VALVE(H) | | | | | | | | | | |
| 0001 | 20 | | GA | | 1-7 | 24-25-12 | D07066 | 6 | | | GD03158 | ST.. | E | | 001-002 |
| 0001 | 20 | | GA | | 1-5 | 24-25-12 | D07066 | 6 | | | GD03158 | ST.. | E | | 115-199 |
| 0002 | 12 | | HA | | 1-7 | 24-25-12 | D07066 | 18 | | | GD03154 | DC.. | E | | 001-002 |
| 0002 | 12 | | HA | | 1-5 | 24-25-12 | D07066 | 18 | | | GD03154 | DC.. | E | | 115-199 |
| 0003 | 12 | | HA | | 1-7 | 24-25-12 | D07066 | 16 | | | GD03154 | DC.. | E | | 001-002 |
| 0003 | 12 | | HA | | 1-5 | 24-25-12 | D07066 | 16 | | | GD03154 | DC.. | E | | 115-199 |
| 0004 | 12 | | HA | | 1-4 | 24-25-12 | SM00001 | | 9 | | D07066 | 20 | | | 001-002, 115-199 |
| 0005 | 12 | | HA | | 1-4 | 24-25-12 | SM00001 | | 9 | | D07066 | 22 | | | 001-002, 115-199 |
| 0006 | 20 | | GA | | 65-10 | 24-25-13 | D40450P | 12 | | | D07074 | 9 | | | ALL |
| 0007 | 20 | | GA | | 1-11 | 24-25-13 | D07074 | 10 | | | GD03160 | DC.. | E | | 001-002, 115-199 |
| 0007 | 20 | | GA | | 1-11 | 24-25-13 | D07074 | 10 | | | GD03160 | DC.. | GW | | 003-099 |
| 0008 | 20 | | GA | | 3-11 | 24-25-12 | D07072 | 4 | | | GD03158 | ST.. | E | | 001-002 |

WIRE LIST

D280N032

91-21-11

Section W2390

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|------|---------|-------------|--------|----|------------------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | | |
| W2396 | 286N2396 | | | | P71 TO HYD MOTOR GEN AND GEN SHUT OFF VALVE(H) (continued) | | | | | | | | | | | | |
| 0008 | 20 | | GA | | 3-8 | 24-25-12 | D07072 | | | | 4 | | GD03158 | ST.. | E | | 115-199 |
| 0009 | 20 | | GA | | 1-11 | 24-25-11 | D07074 | | | | 1 | | GD03160 | DC.. | E | | 001-002, 115-199 |
| 0009 | 20 | | GA | | 1-11 | 24-25-11 | D07074 | | | | 1 | | GD03160 | DC.. | GW | | 003-099 |
| 0010 | 20 | | GA | | 65-10 | 24-25-11 | D40450P | | | | 2 | | D07074 | | 2 | | ALL |
| 0011 | 20 | | GA | | 65-10 | 24-25-11 | D40450P | | | | 1 | | D07074 | | 3 | | ALL |
| 0012 | 06 | | CQ | | 68-2 | 24-25-12 | K10564 | | A1 | F | | | SM00001 | | | 9 | 001-002, 115-199 |
| 0018 | 20 | | GA | | 72-4 | 24-25-12 | D40450P | | | | 11 | | D07072 | | 4 | | 003-099 |
| 0019 | 20 | | GA | | 4-0 | 24-25-12 | D07072 | | | | 5 | | GD03156 | AC.. | GW | | 003-099 |
| 0020 | 12 | | GA | | 1-7 | 24-25-12 | D07066 | | | | 20 | | GD03158 | ST.. | GW | | 003-099 |
| 2501B | 20 | | GF | AC | 70-9 | 24-25-12 | D40450P | | | | 10 | | D07066 | | 4 | | 001-002, 115-199 |
| 2501R | 20 | | GF | AC | 0-0 | 24-25-12 | D40450P | | | | 11 | | D07066 | | 5 | | 001-002, 115-199 |
| 2501Z | | | | AC | 0-0 | 24-25-12 | D40450P | | | | 13 | | D07066 | | 7 | | 001-002, 115-199 |
| 2502B | 20 | | GU | AD | 72-4 | 24-25-12 | D40450P | | | | 9 | | D07072 | | 2 | | 003-099 |
| 2502R | 20 | | GU | AD | 0-0 | 24-25-12 | D40450P | | | | 8 | | D07072 | | 1 | | 003-099 |
| 2502Z | | | | AD | 0-0 | 24-25-12 | D40450P | | | | 10 | | D07072 | DED | | | 003-099 |
| 2503B | 20 | | GU | AF | 70-9 | 24-25-12 | D40450P | | | | 14 | | D07066 | | 25 | | 003-099 |
| 2503R | 20 | | GU | AF | 0-0 | 24-25-12 | D40450P | | | | 13 | | D07066 | | 4 | | 003-099 |
| 2503Z | | | | AF | 0-0 | 24-25-12 | D40450P | | | | 15 | | D07066 | | | AE | 003-099 |
| 3001B | 20 | | GC | AA | 72-9 | 24-25-12 | D40450P | | | | 5 | | D07072 | | 2 | | 001-002, 115-199 |
| 3001R | 20 | | GC | AA | 0-0 | 24-25-12 | D40450P | | | | 4 | | D07072 | | 1 | | 001-002, 115-199 |
| 3001Y | 20 | | GC | AA | 0-0 | 24-25-12 | D40450P | | | | 6 | | D07072 | | 3 | | 001-002, 115-199 |
| 3002B | 20 | | GC | AB | 70-9 | 24-25-12 | D40450P | | | | 7 | | D07066 | | 3 | | 001-002, 115-199 |
| 3002R | 20 | | GC | AB | 0-0 | 24-25-12 | D40450P | | | | 8 | | D07066 | | 1 | | 001-002, 115-199 |
| 3002Y | 20 | | GC | AB | 0-0 | 24-25-12 | D40450P | | | | 9 | | D07066 | | 2 | | 001-002, 115-199 |
| 3501B | 20 | | GV | AE | 70-9 | 24-25-12 | D40450P | | | | 5 | | D07066 | | 2 | | 003-099 |
| 3501R | 20 | | GV | AE | 0-0 | 24-25-12 | D40450P | | | | 4 | | D07066 | | 1 | | 003-099 |
| 3501Y | 20 | | GV | AE | 0-0 | 24-25-12 | D40450P | | | | 6 | | D07066 | | 3 | | 003-099 |
| 3501Z | | | | AE | 0-0 | 24-25-12 | D40450P | | | | 7 | | D07066 | | | AE | 003-099 |
| FRAA | | | | | 0-0 | 24-25-12 | D07066 | | | | 7 | | D07066 | | | AE | 003-099 |
| W2398 | 286N2398 | | | | P71 TO E1-1 | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 22-0 | 24-25-12 | D41390P | | | | 1 | | D41440P | | 1 | | 003-099 |
| 0002 | 20 | | GA | | 22-0 | 24-25-12 | D41390P | | | | 2 | | D41440P | | 2 | | 003-099 |
| 0003 | 20 | | GA | | 22-0 | 24-25-12 | D41390P | | | | 3 | | D41440P | | 3 | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W2390

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|-------------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2400 | 286N2400 | | | L.DUCT LEAK DET. ELEM. TO P54 | | | | | | | | | | | |
| 1001 | 18 | | HE | AA | 13-0 | 26-18-11 | D40478P | 1 | | | D01954 | =1 | | | ALL |
| 1001Z | | | | AA | 0-0 | 26-18-11 | D40478P | S/R | | | GD03319 | ST.. | E | *1 | ALL |
| 1002 | 18 | | HE | AB | 8-0 | 26-18-11 | D40478P | 2 | | | D01956 | =1 | | | ALL |
| 1002Z | | | | AB | 0-0 | 26-18-11 | D40478P | S/R | | | GD02668 | ST.. | E | *1 | ALL |
| 1003 | 18 | | HE | AC | 13-0 | 26-18-11 | D40478P | 3 | | | D01958 | =1 | | | ALL |
| 1003Z | | | | AC | 0-0 | 26-18-11 | D40478P | S/R | | | GD03319 | ST.. | E | *1 | ALL |
| 1004 | 18 | | HE | AD | 8-0 | 26-18-11 | D40478P | 4 | | | D01960 | =1 | | | ALL |
| 1004Z | | | | AD | 0-0 | 26-18-11 | D40478P | S/R | | | GD02668 | ST.. | E | *1 | ALL |
| W2406 | 286N2406 | | | LEFT AIR CONDITIONING BAY | | | | | | | | | | | |
| 0001 | 20 | | GA | | 1-9 | 21-51-11 | D01926 | 2 | | | GD00302 | ST.. | E | *3 | ALL |
| 0007 | 20 | | GA | | 1-9 | 21-51-11 | D01928 | 2 | | | GD00302 | ST.. | E | *1 | ALL |
| 0012 | 20 | | GA | | 2-0 | 36-21-11 | D04700 | 5 | | | GD01187 | ST.. | E | | 001-099 |
| 0012 | 20 | | GA | | 1-6 | 36-21-11 | D01606 | 5 | | | GD00822 | ST.. | E | | 115-199 |
| 0016 | 20 | | GA | | 1-8 | 21-51-12 | D04128 | 2 | | | GD00302 | ST.. | E | *2 | ALL |
| 0046 | 20 | | GA | | 2-4 | 21-51-13 | D02942 | 19 | | | GD01356 | ST.. | E | *1 | ALL |
| 0054 | 20 | | GA | | 2-7 | 21-51-13 | D02944 | 19 | | | GD00727 | ST.. | E | *1 | ALL |
| 0062 | 20 | | GA | | 1-5 | 21-51-13 | D02962 | 13 | | | GD00309 | ST.. | E | *1 | ALL |
| 0066 | 20 | | GA | | 1-5 | 21-51-14 | D04136 | 2 | | | GD00304 | ST.. | E | | ALL |
| 0078 | 20 | | GA | | 2-7 | 21-61-51 | D03314 | 2 | | | GD00301 | ST.. | E | | ALL |
| 0083 | 20 | | GA | | 1-8 | 36-11-12 | GD01896 | ST.. | E | *4 | D02782 | 6 | | | ALL |
| 0089 | 20 | | GA | | 1-6 | 21-52-31 | GD02958 | ST.. | E | | D04642 | 12 | | | 001-008, 115-199 |
| 0089 | 20 | | GA | | 2-5 | 21-52-31 | GD02668 | ST.. | E | | D04642 | 12 | | | 009-099 |
| 0090 | 20 | | GA | | 2-0 | 36-21-11 | D04700 | 5 | | | GD01187 | ST.. | E | | 115-199 |
| 1001 | 20 | | GE | AP | 7-2 | 36-21-11 | SM00009 | | 9 | | D04700 | 3 | | | 115-199 |
| 1001Z | | | | AP | 0-0 | 36-21-11 | SM00010 | | 9 | | GD01187 | ST.. | E | | 115-199 |
| 1002 | 18 | | GE | CF | 18-1 | 33-31-21 | SP01572 | | 9 | | GD00678 | DC.. | E | * | 001-099 |
| 1002 | 18 | | GE | CF | 18-1 | 33-31-21 | SP01572 | | 9 | | GD00678 | DC.. | E | | 115-199 |
| 1002Z | | | | CF | 0-0 | 33-31-21 | GD01197 | ST.. | E | | GD00678 | DC.. | E | * | 001-099 |
| 1002Z | | | | CF | 0-0 | 33-31-21 | GD01197 | ST.. | E | | GD00678 | DC.. | E | | 115-199 |
| 1003 | 20 | | GE | AO | 9-8 | 36-21-11 | D04700 | 3 | | | D40074P | 12 | | | 001-099 |
| 1003 | 20 | | GE | AO | 3-0 | 36-21-11 | SM00009 | | 9 | | D40074P | 12 | | | 115-199 |
| 1003Z | | | | AO | 0-0 | 36-21-11 | GD01187 | ST.. | E | | D40074P | S/R | | | 001-099 |
| 1003Z | | | | AO | 0-0 | 36-21-11 | SM00010 | | 9 | | D40074P | S/R | | | 115-199 |
| 1004 | 18 | | GE | AZ | 11-3 | 21-51-11 | D01930 | 2 | 18 | | D41100P | 24 | 18 | | ALL |
| 1004Z | | | | AZ | 0-0 | 21-51-11 | GD00308 | ST.. | E | | D41100P | S/R | | | ALL |
| 1005 | 20 | | GE | AJ | 10-3 | 21-51-11 | D01930 | 1 | | | GD02821 | DC.. | E | *1 | ALL |
| 1005Z | | | | AJ | 0-0 | 21-51-11 | GD00308 | ST.. | E | | GD02821 | DC.. | E | *1 | ALL |
| 1006 | 18 | | GE | BP | 4-0 | 33-31-21 | S00362 | 2 | C | | S00361 | 2 | C | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2400

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2406 | 286N2406 | LEFT AIR CONDITIONING BAY (continued) | | | | | | | | | | | | | |
| 1006Z | | BP | 0-0 | 33-31-21 | GD00217 | ST.. | E | | GD01196 | ST.. | E | | 115-199 | | |
| 1008 | 18 | GE BK | 18-3 | 33-31-21 | SP00332 | | 9 | | S00361 | 3 | C | | ALL | | |
| 1008Z | | BK | 0-0 | 33-31-21 | GD01197 | ST.. | E | | GD01196 | ST.. | E | | ALL | | |
| 1009 | 18 | GE CE | 22-0 | 33-31-21 | D41100P | | 15 | | S00361 | 2 | C | | ALL | | |
| 1009Z | | CE | 0-0 | 33-31-21 | D41100P | S/R | | | GD01196 | ST.. | E | | ALL | | |
| 1010 | 20 | GE AW | 13-1 | 21-51-11 | D01926 | | 3 | | GD02821 | DC.. | E | *2 | ALL | | |
| 1010Z | | AW | 0-0 | 21-51-11 | GD00302 | ST.. | E | *3 | GD02821 | DC.. | E | *2 | ALL | | |
| 1011 | 20 | GE AN | 9-8 | 21-51-11 | D01926 | | 1 | | D41100P | 18 | | | ALL | | |
| 1011Z | | AN | 0-0 | 21-51-11 | GD00302 | ST.. | E | *3 | D41100P | S/R | | | ALL | | |
| 1012 | 20 | GE AQ | 13-1 | 21-51-11 | D01928 | | 3 | | GD02821 | DC.. | E | *3 | ALL | | |
| 1012Z | | AQ | 0-0 | 21-51-11 | GD00302 | ST.. | E | *1 | GD02821 | DC.. | E | *3 | ALL | | |
| 1013 | 20 | GE AS | 19-6 | 21-51-13 | D02944 | | 1 | | GD02811 | AC.. | E | *1 | ALL | | |
| 1013Z | | AS | 0-0 | 21-51-13 | GD00727 | ST.. | E | *3 | GD02811 | AC.. | E | *1 | ALL | | |
| 1014 | 20 | GE CD | 3-4 | 36-21-11 | D04700 | | 4 | | GD02857 | DC.. | E | | 001-099 | | |
| 1014 | 20 | GE CD | 20-1 | 36-21-11 | D01606 | | 4 | | GD02823 | DC.. | E | | 115-199 | | |
| 1014Z | | CD | 0-0 | 36-21-11 | GD01187 | ST.. | E | | GD02857 | DC.. | E | | 001-099 | | |
| 1014Z | | CD | 0-0 | 36-21-11 | GD00822 | ST.. | E | *1 | GD02823 | DC.. | E | | 115-199 | | |
| 1015 | 20 | GE AT | 20-1 | 21-51-13 | D02942 | | 1 | | GD02811 | AC.. | E | *2 | ALL | | |
| 1015Z | | AT | 0-0 | 21-51-13 | GD01356 | ST.. | E | *2 | GD02811 | AC.. | E | *2 | ALL | | |
| 1016 | 20 | GE BU | 9-0 | 21-51-13 | D02962 | | 3 | | GD02811 | AC.. | E | *3 | ALL | | |
| 1016Z | | BU | 0-0 | 21-51-13 | GD00309 | ST.. | E | *2 | GD02811 | AC.. | E | *3 | ALL | | |
| 1017 | 20 | GE CA | 13-8 | 21-51-15 | D02968 | | 1 | | D41100P | 8 | | | ALL | | |
| 1017Z | | CA | 0-0 | 21-51-15 | GD02691 | ST.. | E | | D41100P | S/R | | | ALL | | |
| 1018 | 20 | GE BV | 17-0 | 21-51-15 | D02968 | | 2 | | GD02817 | DC.. | E | *1 | ALL | | |
| 1018Z | | BV | 0-0 | 21-51-15 | GD02691 | ST.. | E | | GD02817 | DC.. | E | *1 | ALL | | |
| 1019 | 20 | GE CB | 14-4 | 21-51-15 | D04194 | | 1 | | D41100P | 9 | | | ALL | | |
| 1019Z | | CB | 0-0 | 21-51-15 | GD02683 | ST.. | E | | D41100P | S/R | | | ALL | | |
| 1020 | 20 | GE BW | 8-0 | 21-51-15 | D04194 | | 2 | | GD02819 | DC.. | E | *1 | ALL | | |
| 1020Z | | BW | 0-0 | 21-51-15 | GD02683 | ST.. | E | | GD02819 | DC.. | E | *1 | ALL | | |
| 1021 | 20 | GT BS | 4-7 | 36-22-11 | D40072P | | 35 | | D07418 | 1 | | | 001-099 | | |
| 1021 | 20 | GE BS | 4-7 | 36-22-11 | D40072P | | 35 | | D07418 | 1 | | | 115-199 | | |
| 1021Z | | BS | 0-0 | 36-22-11 | D40072P | S/R | | | GD03520 | ST.. | E | | 001-099 | | |
| 1021Z | | BS | 0-0 | 36-22-11 | GD03520 | ST.. | E | | D40072P | S/R | | | 115-199 | | |
| 1022 | 20 | GT DL | 4-1 | 36-22-11 | D07418 | | 2 | | GD03522 | DC.. | E | | 001-099 | | |
| 1022 | 20 | GE CW | 4-1 | 36-22-11 | D07418 | | 2 | | GD03522 | DC.. | E | | 115-199 | | |
| 1022Z | | DL | 0-0 | 36-22-11 | GD03520 | ST.. | E | | GD03522 | DC.. | E | | 001-099 | | |
| 1022Z | | CW | 0-0 | 36-22-11 | GD03520 | ST.. | E | | GD03522 | DC.. | E | | 115-199 | | |
| 1023 | 20 | GE BR | 2-9 | 21-61-51 | D03314 | | 3 | | GD02857 | DC.. | E | | ALL | | |
| 1023Z | | BR | 0-0 | 21-61-51 | GD00301 | ST.. | E | | GD02857 | DC.. | E | | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W2400

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|---------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2406 | 286N2406 | | | LEFT AIR CONDITIONING BAY (continued) | | | | | | | | | | | |
| 1024 | 20 | GE | BY | 11-5 | 21-61-51 | D03314 | 1 | | | | D41100P | 7 | | | ALL |
| 1024Z | | | BY | 0-0 | 21-61-51 | GD00301 | ST.. | E | | | D41100P | S/R | | | ALL |
| 1030 | 20 | GE | CT | 2-7 | 36-21-11 | D01606 | 3 | | | | SM00009 | | 9 | | 115-199 |
| 1030Z | | | CT | 0-0 | 36-21-11 | GD00822 | ST.. | E | *1 | | SM00010 | | 9 | | 115-199 |
| 1035 | 20 | GE | AU | 20-9 | 21-51-13 | D02942 | 15 | | | | GD02827 | DC.. | E | *1 | ALL |
| 1035Z | | | AU | 0-0 | 21-51-13 | GD01356 | ST.. | E | *3 | | GD02827 | DC.. | E | *1 | ALL |
| 1036 | 20 | GE | CG | 20-9 | 21-51-13 | D02942 | 18 | | | | GD02827 | DC.. | E | *2 | ALL |
| 1036Z | | | CG | 0-0 | 21-51-13 | GD01356 | ST.. | E | *3 | | GD02827 | DC.. | E | *2 | ALL |
| 1037 | 20 | GE | AV | 20-0 | 21-51-13 | D02944 | 15 | | | | GD02823 | DC.. | E | *1 | ALL |
| 1037Z | | | AV | 0-0 | 21-51-13 | GD00727 | ST.. | E | | | GD02823 | DC.. | E | *1 | ALL |
| 1038 | 20 | GE | CH | 20-0 | 21-51-13 | D02944 | 18 | | | | GD02823 | DC.. | E | *2 | ALL |
| 1038Z | | | CH | 0-0 | 21-51-13 | GD00727 | ST.. | E | *3 | | GD02823 | DC.. | E | *2 | ALL |
| 1039 | 20 | GE | BT | 9-9 | 21-51-13 | D02962 | 8 | | | | GD02829 | DC.. | E | *1 | ALL |
| 1039Z | | | BT | 0-0 | 21-51-13 | GD00309 | ST.. | E | *1 | | GD02829 | DC.. | E | *1 | ALL |
| 1040 | 20 | GE | CJ | 9-9 | 21-51-13 | D02962 | 11 | | | | GD02829 | DC.. | E | *2 | ALL |
| 1040Z | | | CJ | 0-0 | 21-51-13 | GD00309 | ST.. | E | *1 | | GD02829 | DC.. | E | *2 | ALL |
| 2501B | 18 | GF | AX | 9-7 | 21-51-11 | D01928 | 5 | 18 | | | D41100P | 19 | | | ALL |
| 2501R | 18 | GF | AX | 0-0 | 21-51-11 | D01928 | 1 | 18 | | | D41100P | 23 | | | ALL |
| 2501Z | | | AX | 0-0 | 21-51-11 | GD00302 | ST.. | E | *1 | | D41100P | S/R | | | ALL |
| 2502B | 20 | GF | BL | 5-4 | 21-51-13 | D02944 | 3 | | | | D40072P | 15 | | | ALL |
| 2502R | 20 | GF | BL | 0-0 | 21-51-13 | D02944 | 2 | | | | D40072P | 27 | | | ALL |
| 2502Z | | | BL | 0-0 | 21-51-13 | GD00727 | ST.. | E | *3 | | D40072P | S/R | | | ALL |
| 2503B | 20 | GF | AI | 9-1 | 21-51-12 | D04128 | 1 | | | | D40072P | 46 | | | ALL |
| 2503R | 20 | GF | AI | 0-0 | 21-51-12 | D04128 | 3 | | | | D40072P | 45 | | | ALL |
| 2503Z | | | AI | 0-0 | 21-51-12 | GD00302 | ST.. | E | *2 | | D40072P | S/R | | | ALL |
| 2504B | 20 | GF | BB | 12-5 | 21-51-12 | D02952 | 1 | | | | D40072P | 32 | | | ALL |
| 2504R | 20 | GF | BB | 0-0 | 21-51-12 | D02952 | 2 | | | | D40072P | 31 | | | ALL |
| 2504Z | | | BB | 0-0 | 21-51-12 | D40072P | S/R | | | | GD00303 | ST.. | E | | ALL |
| 2505B | 20 | GF | BE | 13-7 | 21-51-15 | D02966 | 1 | | | | D40072P | 52 | | | ALL |
| 2505R | 20 | GF | BE | 0-0 | 21-51-15 | D02966 | 2 | | | | D40072P | 53 | | | ALL |
| 2505Z | | | BE | 0-0 | 21-51-15 | GD02683 | ST.. | E | | | D40072P | S/R | | | ALL |
| 2506B | 20 | GF | BI | 20-6 | 21-51-13 | D02942 | 3 | | | | D40072P | 28 | | | ALL |
| 2506R | 20 | GF | BI | 0-0 | 21-51-13 | D02942 | 2 | | | | D40072P | 29 | | | ALL |
| 2506Z | | | BI | 0-0 | 21-51-13 | GD01356 | ST.. | E | *2 | | D40072P | S/R | | | ALL |
| 2507B | 20 | GF | BJ | 21-0 | 21-51-13 | D02942 | 13 | | | | D41100P | 3 | | | ALL |
| 2507R | 20 | GF | BJ | 0-0 | 21-51-13 | D02942 | 16 | | | | D41100P | 4 | | | ALL |
| 2507Z | | | BJ | 0-0 | 21-51-13 | GD01356 | ST.. | E | | | D41100P | S/R | | | ALL |
| 2509B | 20 | GF | BM | 6-4 | 21-51-13 | D02944 | 13 | | | | D41100P | 1 | | | ALL |
| 2509R | 20 | GF | BM | 0-0 | 21-51-13 | D02944 | 16 | | | | D41100P | 2 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2400

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|--|------------------------|------------------------|---------------------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W2406 | 286N2406 | LEFT AIR CONDITIONING BAY (continued) | | | |
| 2509Z | | BM | 0-0 21-51-13 GD00727 | ST.. E *3 D41100P | S/R ALL |
| 2511B | 20 | GF BO | 15-6 21-51-13 D02962 | 6 D41100P | 5 ALL |
| 2511R | 20 | GF BO | 0-0 21-51-13 D02962 | 9 D41100P | 6 ALL |
| 2511Z | | BO | 0-0 21-51-13 GD00309 | ST.. E *1 D41100P | S/R ALL |
| 2513B | 20 | GF BQ | 15-1 21-51-13 D02962 | 1 D40072P | 25 ALL |
| 2513R | 20 | GF BQ | 0-0 21-51-13 D02962 | 2 D40072P | 26 ALL |
| 2513Z | | BQ | 0-0 21-51-13 GD00309 | ST.. E *2 D40072P | S/R ALL |
| 2514B | 20 | GF AB | 9-8 36-21-11 D04700 | 2 D40074P | 24 001-099 |
| 2514B | 20 | GF AB | 5-0 36-21-11 D01606 | 2 D40074P | 24 115-199 |
| 2514R | 20 | GF AB | 0-0 36-21-11 D04700 | 1 D40074P | 23 001-099 |
| 2514R | 20 | GF AB | 0-0 36-21-11 D01606 | 1 D40074P | 23 115-199 |
| 2514Z | | AB | 0-0 36-21-11 GD01187 | ST.. E *1 D40074P | S/R 001-099 |
| 2514Z | | AB | 0-0 36-21-11 GD00822 | ST.. E *1 D40074P | S/R 115-199 |
| 2517B | 20 | GF AA | 12-8 21-51-14 D04132 | 2 D40072P | 39 ALL |
| 2517R | 20 | GF AA | 0-0 21-51-14 D04132 | 1 D40072P | 38 ALL |
| 2517Z | | AA | 0-0 21-51-14 GD00303 | ST.. E D40072P | S/R ALL |
| 2518B | 20 | GF BC | 14-7 21-51-14 D04134 | 2 D40072P | 49 ALL |
| 2518R | 20 | GF BC | 0-0 21-51-14 D04134 | 1 D40072P | 47 ALL |
| 2518Z | | BC | 0-0 21-51-14 GD00306 | ST.. E D40072P | S/R ALL |
| 2519B | 20 | GF BD | 15-11 21-51-14 D04136 | 1 D40072P | 51 ALL |
| 2519R | 20 | GF BD | 0-0 21-51-14 D04136 | 3 D40072P | 50 ALL |
| 2519Z | | BD | 0-0 21-51-14 GD00304 | ST.. E D40072P | S/R ALL |
| 2521B | 20 | GF BH | 15-5 36-11-12 D40074P | 13 D02782 | 3 ALL |
| 2521R | 20 | GF BH | 0-0 36-11-12 D40074P | 14 D02782 | 2 ALL |
| 2521Z | | BH | 0-0 36-11-12 D40074P | S/R GD01896 | ST.. E *4 ALL |
| 2522B | 20 | GF AK | 10-3 21-52-31 D40074P | 18 D04642 | 2 001-008, 115-199 |
| 2522B | 20 | GF AK | 7-4 21-52-31 D40074P | 18 D04642 | 2 009-099 |
| 2522R | 20 | GF AK | 0-0 21-52-31 D40074P | 19 D04642 | 1 ALL |
| 2522Z | | AK | 0-0 21-52-31 D40074P | S/R GD02958 | ST.. E * 001-008, 115-199 |
| 2522Z | | AK | 0-0 21-52-31 D40074P | S/R GD02668 | ST.. E * 009-099 |
| 2523B | 20 | GF AL | 10-3 21-52-31 D40074P | 20 D04642 | 9 001-008, 115-199 |
| 2523B | 20 | GF AL | 7-4 21-52-31 D40074P | 20 D04642 | 9 009-099 |
| 2523R | 20 | GF AL | 0-0 21-52-31 D40074P | 21 D04642 | 8 ALL |
| 2523Z | | AL | 0-0 21-52-31 D40074P | S/R GD02958 | ST.. E * 001-008, 115-199 |
| 2523Z | | AL | 0-0 21-52-31 D40074P | S/R GD02668 | ST.. E * 009-099 |
| 2524B | 20 | GF AM | 9-8 36-21-11 D40074P | 34 D04700 | 2 115-199 |
| 2524R | 20 | GF AM | 0-0 36-21-11 D40074P | 35 D04700 | 1 115-199 |
| 2524Z | | AM | 0-0 36-21-11 D40074P | S/R GD01187 | ST.. E 115-199 |
| 2541B | 20 | GF CW | 13-5 21-52-11 D40074P | 16 D05330 | A 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2400

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2406 | 286N2406 | | | LEFT AIR CONDITIONING BAY (continued) | | | | | | | | | | | |
| 2541R | 20 | GF | CW | | 0-0 | 21-52-11 | D40074P | 17 | | | D05330 | B | | | 001-099 |
| 2541Z | | | CW | | 0-0 | 21-52-11 | D40074P | S/R | | | GD02683 | ST.. | E | | 001-099 |
| 2542B | 20 | GF | CX | | 12-10 | 21-52-11 | D40074P | 1 | | | D03396 | A | | | ALL |
| 2542R | 20 | GF | CX | | 0-0 | 21-52-11 | D40074P | 2 | | | D03396 | B | | | ALL |
| 2542Z | | | CX | | 0-0 | 21-52-11 | D40074P | S/R | | | GD02691 | ST.. | E | | ALL |
| 2543B | 20 | GF | CY | | 14-10 | 21-52-11 | D40074P | 3 | | | D03120 | A | | | 001-099 |
| 2543R | 20 | GF | CY | | 0-0 | 21-52-11 | D40074P | 4 | | | D03120 | B | | | 001-099 |
| 2543Z | | | CY | | 0-0 | 21-52-11 | D40074P | S/R | | | GD01434 | ST.. | E | | 001-099 |
| 2544B | 20 | GF | CZ | | 14-7 | 21-52-11 | D40074P | 5 | | | D03122 | A | | | 001-099 |
| 2544R | 20 | GF | CZ | | 0-0 | 21-52-11 | D40074P | 6 | | | D03122 | B | | | 001-099 |
| 2544Z | | | CZ | | 0-0 | 21-52-11 | D40074P | S/R | | | GD00306 | ST.. | E | | 001-099 |
| 2545B | 20 | GF | DA | | 14-7 | 21-52-11 | D40074P | 7 | | | D03124 | A | | | 001-099 |
| 2545R | 20 | GF | DA | | 0-0 | 21-52-11 | D40074P | 9 | | | D03124 | B | | | 001-099 |
| 2545Z | | | DA | | 0-0 | 21-52-11 | D40074P | S/R | | | GD00306 | ST.. | E | | 001-099 |
| 2546B | 20 | GF | DB | | 14-6 | 21-52-11 | D40074P | 10 | | | D03126 | A | | | 001-099 |
| 2546R | 20 | GF | DB | | 0-0 | 21-52-11 | D40074P | 11 | | | D03126 | B | | | 001-099 |
| 2546Z | | | DB | | 0-0 | 21-52-11 | D40074P | S/R | | | GD00306 | ST.. | E | | 001-099 |
| 3501B | 20 | GG | AC | | 20-6 | 21-51-12 | D02942 | 10 | | | D40072P | 4 | | | ALL |
| 3501R | 20 | GG | AC | | 0-0 | 21-51-12 | D02942 | 11 | | | D40072P | 5 | | | ALL |
| 3501Y | 20 | GG | AC | | 0-0 | 21-51-12 | D02942 | 12 | | | D40072P | 6 | | | ALL |
| 3501Z | | | AC | | 0-0 | 21-51-12 | GD01356 | ST.. | E | *1 | D40072P | S/R | | | ALL |
| 3502B | 20 | GG | AD | | 20-6 | 21-51-12 | D02942 | 5 | | | D40072P | 2 | | | ALL |
| 3502R | 20 | GG | AD | | 0-0 | 21-51-12 | D02942 | 4 | | | D40072P | 1 | | | ALL |
| 3502Y | 20 | GG | AD | | 0-0 | 21-51-12 | D02942 | 6 | | | D40072P | 3 | | | ALL |
| 3502Z | | | AD | | 0-0 | 21-51-12 | GD01356 | ST.. | E | *2 | D40072P | S/R | | | ALL |
| 3503B | 20 | GG | AE | | 5-4 | 21-51-12 | D02944 | 10 | | | D40072P | 12 | | | ALL |
| 3503R | 20 | GG | AE | | 0-0 | 21-51-12 | D02944 | 11 | | | D40072P | 11 | | | ALL |
| 3503Y | 20 | GG | AE | | 0-0 | 21-51-12 | D02944 | 12 | | | D40072P | 13 | | | ALL |
| 3503Z | | | AE | | 0-0 | 21-51-12 | GD00727 | ST.. | E | *1 | D40072P | S/R | | | ALL |
| 3504B | 20 | GG | AF | | 5-4 | 21-51-12 | D02944 | 5 | | | D40072P | 9 | | | ALL |
| 3504R | 20 | GG | AF | | 0-0 | 21-51-12 | D02944 | 4 | | | D40072P | 8 | | | ALL |
| 3504Y | 20 | GG | AF | | 0-0 | 21-51-12 | D02944 | 6 | | | D40072P | 10 | | | ALL |
| 3504Z | | | AF | | 0-0 | 21-51-12 | GD00727 | ST.. | E | *2 | D40072P | S/R | | | ALL |
| 3505B | 20 | GG | AG | | 15-1 | 21-51-12 | D02962 | 5 | | | D40072P | 18 | | | ALL |
| 3505R | 20 | GG | AG | | 0-0 | 21-51-12 | D02962 | 4 | | | D40072P | 19 | | | ALL |
| 3505Y | 20 | GG | AG | | 0-0 | 21-51-12 | D02962 | 12 | | | D40072P | 20 | | | ALL |
| 3505Z | | | AG | | 0-0 | 21-51-12 | GD00309 | ST.. | E | | D40072P | S/R | | | ALL |
| 3506B | 20 | GG | AH | | 15-6 | 21-51-12 | D02946 | 4 | | | D40072P | 16 | | | ALL |
| 3506R | 20 | GG | AH | | 0-0 | 21-51-12 | D02946 | 2 | | | D40072P | 7 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2400

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2406 | 286N2406 | | | LEFT AIR CONDITIONING BAY (continued) | | | | | | | | | | | |
| 3506Y | 20 | GG | AH | | 0-0 | 21-51-12 | D02946 | 6 | | | D40072P | 17 | | | ALL |
| 3506Z | | | AH | | 0-0 | 21-51-12 | GD00304 | ST.. | E | | D40072P | S/R | | | ALL |
| 3507B | 20 | GG | AY | | 4-11 | 21-52-21 | D02944 | 8 | | | D40074P | 28 | | | ALL |
| 3507R | 20 | GG | AY | | 0-0 | 21-52-21 | D02944 | 7 | | | D40074P | 27 | | | ALL |
| 3507Y | 20 | GG | AY | | 0-0 | 21-52-21 | D02944 | 9 | | | D40074P | 29 | | | ALL |
| 3507Z | | | AY | | 0-0 | 21-52-21 | GD00727 | ST.. | E | *2 | D40074P | S/R | | | ALL |
| 3509B | 20 | GG | BA | | 5-3 | 21-51-12 | D04114 | 2 | | | D40072P | 37 | | | ALL |
| 3509R | 20 | GG | BA | | 0-0 | 21-51-12 | D04114 | 1 | | | D40072P | 34 | | | ALL |
| 3509Y | 20 | GG | BA | | 0-0 | 21-51-12 | D04114 | 3 | | | D40072P | 36 | | | ALL |
| 3509Z | | | BA | | 0-0 | 21-51-12 | GD00822 | ST.. | E | | D40072P | S/R | | | ALL |
| 3510B | 20 | GG | BF | | 15-1 | 21-52-21 | D02946 | 3 | | | D40074P | 39 | | | ALL |
| 3510R | 20 | GG | BF | | 0-0 | 21-52-21 | D02946 | 1 | | | D40074P | 38 | | | ALL |
| 3510Y | 20 | GG | BF | | 0-0 | 21-52-21 | D02946 | 5 | | | D40074P | 40 | | | ALL |
| 3510Z | | | BF | | 0-0 | 21-52-21 | GD00304 | ST.. | E | | D40074P | S/R | | | ALL |
| 4255B | 20 | GH | BG | | 10-3 | 21-52-31 | D04642 | 3 | | | D40074P | 32 | | | 001-008, 115-199 |
| 4255B | 20 | GH | BG | | 7-4 | 21-52-31 | D04642 | 3 | | | D40074P | 32 | | | 009-099 |
| 4255G | 20 | GH | BG | | 0-0 | 21-52-31 | D04642 | 5 | | | D40074P | 30 | | | ALL |
| 4255R | 20 | GH | BG | | 0-0 | 21-52-31 | D04642 | 4 | | | D40074P | 31 | | | ALL |
| 4255Y | 20 | GH | BG | | 0-0 | 21-52-31 | D04642 | 6 | | | D40074P | 33 | | | ALL |
| 4255Z | | | BG | | 0-0 | 21-52-31 | GD02958 | ST.. | E | | D40074P | S/R | | | 001-008, 115-199 |
| 4255Z | | | BG | | 0-0 | 21-52-31 | GD02668 | ST.. | E | | D40074P | S/R | | | 009-099 |
| A-BK | | | | | 0-6 | 33-31-21 | SP00332 | | 9 | | L00344 | BLK | | | ALL |
| A-WT | | | | | 0-0 | 33-31-21 | L00344 | WHT | | | SP01572 | | 9 | | ALL |
| B-BK | | | | | 0-6 | 33-31-21 | S00361 | 3 | C | | L00345 | BLK | | | ALL |
| B-WT | | | | | 0-0 | 33-31-21 | L00345 | WHT | | | GD00678 | DC.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2400

Page 6 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W2410 | 286N2410 | | | LEFT WHEEL WELL- LIGHTING & FLIGHT CONTROLS | | | | | | | | | | | | |
| 0008 | 18 | GA | | | 4-0 | 27-51-21 | D01716 | 1 | | | | GD00911 | DC.. | E | | ALL |
| 0015 | 18 | GA | | | 3-0 | 22-11-22 | D00065 | 19 | | | | GD01075 | ST.. | E | | ALL |
| 0020 | 18 | GA | | | 2-0 | 27-51-11 | D01714 | 8 | | | | GD00830 | ST.. | E | *1 | ALL |
| 0023 | 20 | GA | | | 3-0 | 27-51-21 | D01716 | 5 | | | | SM00030 | | 9 | | ALL |
| 0037 | 18 | GA | | | 3-0 | 27-51-11 | D01806 | 7 | | | | GD00829 | ST.. | E | | ALL |
| 0041 | 20 | GA | | | 2-0 | 27-51-21 | SM00030 | | 9 | | | D01714 | 6 | | | ALL |
| 0042 | 16 | GA | | | 3-0 | 33-31-11 | L00077 | =G | E | | | GD00905 | AC.. | E | | ALL |
| 0043 | 16 | GA | | | 2-0 | 33-31-11 | L00076 | =G | E | | | GD00020 | AC.. | E | | ALL |
| 0045 | 18 | GA | | | 3-0 | 22-11-22 | D00065 | 17 | | | | GD01418 | DC.. | E | | ALL |
| 0046 | 18 | GA | | | 3-0 | 22-11-22 | D00065 | 1 | | | | GD01418 | DC.. | E | | ALL |
| 1001 | 14 | GE | AN | | 12-0 | 27-51-11 | D40342P | 15 | | | | D01714 | 1 | | | ALL |
| 1001Z | | | AN | | 0-0 | 27-51-11 | D40342P | S/R | | | | GD00830 | ST.. | E | *1 | ALL |
| 1002 | 14 | GE | AO | | 12-0 | 27-51-11 | D40342P | 19 | | | | D01714 | 3 | | | ALL |
| 1002Z | | | AO | | 0-0 | 27-51-11 | D40342P | S/R | | | | GD00830 | ST.. | E | *2 | ALL |
| 1003 | 14 | GE | AQ | | 12-0 | 27-51-11 | D40342P | 23 | | | | D01714 | 2 | | | ALL |
| 1003Z | | | AQ | | 0-0 | 27-51-11 | D40342P | S/R | | | | GD00830 | ST.. | E | *2 | ALL |
| 1004 | 16 | GE | AL | | 18-0 | 33-31-11 | L00077 | =P | C | *2 | | L00076 | =P | C | | 001-099 |
| 1004 | 16 | GE | AL | | 17-0 | 33-31-11 | L00077 | =P | C | *2 | | L00076 | =P | C | | 115-199 |
| 1004Z | | | AL | | 0-0 | 33-31-11 | GD00823 | ST.. | E | | | GD01098 | ST.. | E | | ALL |
| 1005 | 20 | GE | AT | | 12-0 | 27-51-21 | D40342P | 10 | | | | D01714 | 7 | | | ALL |
| 1005Z | | | AT | | 0-0 | 27-51-21 | D40342P | S/R | | | | GD00829 | ST.. | E | | ALL |
| 1006 | 20 | GE | AS | | 11-0 | 27-51-21 | D40342P | 9 | | | | SM00030 | | 9 | | 001-099 |
| 1006 | 20 | GE | AS | | 12-0 | 27-51-21 | D40342P | 9 | | | | SM00030 | | 9 | | 115-199 |
| 1006Z | | | AS | | 0-0 | 27-51-21 | D40342P | S/R | | | | GD01093 | ST.. | E | | ALL |
| 1013 | 16 | GE | AK | | 35-0 | 33-31-11 | L00077 | =P | C | *2 | | L00073 | =P | C | | 001-099 |
| 1013 | 16 | GE | AK | | 33-0 | 33-31-11 | L00077 | =P | C | *2 | | L00073 | =P | C | | 115-199 |
| 1013Z | | | AK | | 0-0 | 33-31-11 | GD00823 | ST.. | E | | | GD01630 | ST.. | E | | ALL |
| 1020 | 18 | GE | AE | | 14-0 | 22-11-22 | D40342P | 14 | 18 | | | D00065 | 2 | | | 001-099 |
| 1020 | 18 | GE | AE | | 15-0 | 22-11-22 | D40342P | 14 | 18 | | | D00065 | 2 | | | 115-199 |
| 1020Z | | | AE | | 0-0 | 22-11-22 | D40342P | S/R | | | | GD01075 | ST.. | E | *1 | ALL |
| 1021 | 18 | GE | BF | | 14-0 | 22-11-22 | D40342P | 18 | 18 | | | D00065 | 18 | | | 001-099 |
| 1021 | 18 | GE | BF | | 15-0 | 22-11-22 | D40342P | 18 | 18 | | | D00065 | 18 | | | 115-199 |
| 1021Z | | | BF | | 0-0 | 22-11-22 | D40342P | S/R | | | | GD01075 | ST.. | E | *3 | 001-099 |
| 1021Z | | | BF | | 0-0 | 22-11-22 | D40342P | S/R | | | | GD01075 | ST.. | E | *1 | 115-199 |
| 2002B | 20 | GB | AB | | 0-6 | 22-11-21 | D00065 | 12 | | | | SM00001 | | 9 | | ALL |
| 2002R | 20 | GB | AB | | 0-0 | 22-11-21 | D00065 | 13 | | | | SM00002 | | 9 | | ALL |
| 2003B | 20 | GB | AC | | 0-6 | 22-11-21 | D00065 | 7 | | | | SM00001 | | 9 | | ALL |
| 2003R | 20 | GB | AC | | 0-0 | 22-11-21 | D00065 | 8 | | | | SM00002 | | 9 | | ALL |
| 2501B | 20 | GF | AF | | 12-0 | 27-51-11 | D40342P | 28 | | | | D01806 | 2 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 1

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2410
Page 2
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|-------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2412 | 286N2412 | | | LEFT WHEEL WELL- ANTI-SKID AND HYDRAULICS (continued) | | | | | | | | | | | |
| 0005 | 20 | | GA | | 1-11 | 32-42-11 | D02034 | | | AE | GD01617 | ST.. | E | | 001-099 |
| 0005 | 20 | | GA | | 3-0 | 32-42-11 | D02034 | | | AE | GD01617 | ST.. | E | | 115-199 |
| 0006 | 20 | | GA | | 1-8 | 32-42-11 | D02032 | | | AF | GD01617 | ST.. | E | | 001-099 |
| 0006 | 20 | | GA | | 2-0 | 32-42-11 | D02032 | | | AF | GD01617 | ST.. | E | | 115-199 |
| 0007 | 20 | | GA | | 1-9 | 32-42-11 | D02030 | | | AG | GD01762 | ST.. | E | | 001-099 |
| 0007 | 20 | | GA | | 2-0 | 32-42-11 | D02030 | | | AG | GD01762 | ST.. | E | | 115-199 |
| 0008 | 20 | | GA | | 2-0 | 32-42-11 | D02028 | | | AH | GD01762 | ST.. | E | | ALL |
| 0009 | 18 | | GA | | 2-4 | 29-32-41 | SM00REF | | 1 | AP | GD01659 | ST.. | E | | 001-099 |
| 0009 | 18 | | GA | | 4-0 | 29-32-41 | SM00REF | | 1 | AP | GD01659 | ST.. | E | | 115-199 |
| 0035 | 18 | | GA | | 1-10 | 32-42-11 | V00038 | = GND | E | | GD01762 | ST.. | E | *2 | 001-099 |
| 0035 | 18 | | GA | | 3-0 | 32-42-11 | V00038 | = GND | E | | GD01762 | ST.. | E | *2 | 115-199 |
| 0036 | 18 | | GA | | 2-9 | 32-42-11 | V00030 | = GND | E | | GD01621 | ST.. | E | *1 | 001-099 |
| 0036 | 18 | | GA | | 4-0 | 32-42-11 | V00030 | = GND | E | | GD01621 | ST.. | E | *1 | 115-199 |
| 0037 | 18 | | GA | | 3-1 | 32-42-11 | V00032 | = GND | E | | GD01621 | ST.. | E | *1 | 001-099 |
| 0037 | 18 | | GA | | 4-0 | 32-42-11 | V00032 | = GND | E | | GD01621 | ST.. | E | *1 | 115-199 |
| 0038 | 18 | | GA | | 2-1 | 32-42-11 | V00037 | = GND | E | | GD01762 | ST.. | E | *2 | 001-099 |
| 0038 | 18 | | GA | | 3-0 | 32-42-11 | V00037 | = GND | E | | GD01762 | ST.. | E | *2 | 115-199 |
| 0039 | 18 | | GA | | 2-7 | 32-42-11 | V00029 | = GND | E | | GD01621 | ST.. | E | *1 | 001-099 |
| 0039 | 18 | | GA | | 4-0 | 32-42-11 | V00029 | = GND | E | | GD01621 | ST.. | E | *1 | 115-199 |
| 0040 | 18 | | GA | | 2-11 | 32-42-11 | V00031 | = GND | E | | GD01621 | ST.. | E | *1 | 001-099 |
| 0040 | 18 | | GA | | 4-0 | 32-42-11 | V00031 | = GND | E | | GD01621 | ST.. | E | *1 | 115-199 |
| 0042 | 18 | | GA | | 0-14 | 29-11-12 | D03102 | | 2 | | GD01558 | DC.. | E | | ALL |
| 0050 | 18 | | GA | | 1-9 | 32-42-11 | D02030 | | 3 | | GD01762 | ST.. | E | *1 | 001-099 |
| 0050 | 18 | | GA | | 4-0 | 32-42-11 | D02030 | | 3 | | GD01762 | ST.. | E | *2 | 115-199 |
| 0051 | 18 | | GA | | 2-5 | 32-42-11 | D02034 | | 3 | | GD01656 | ST.. | E | *1 | 001-099 |
| 0051 | 18 | | GA | | 3-0 | 32-42-11 | D02034 | | 3 | | GD01656 | ST.. | E | *1 | 115-199 |
| 0052 | 18 | | GA | | 2-9 | 32-42-11 | D02038 | | 3 | | GD01656 | ST.. | E | *1 | 001-099 |
| 0052 | 18 | | GA | | 3-0 | 32-42-11 | D02038 | | 3 | | GD01656 | ST.. | E | *1 | 115-199 |
| 0053 | 18 | | GA | | 2-0 | 32-42-11 | D02028 | | 3 | | GD01762 | ST.. | E | *1 | 001-099 |
| 0053 | 18 | | GA | | 3-0 | 32-42-11 | D02028 | | 3 | | GD01762 | ST.. | E | *2 | 115-199 |
| 0054 | 18 | | GA | | 2-2 | 32-42-11 | D02032 | | 3 | | GD01656 | ST.. | E | *2 | 001-099 |
| 0054 | 18 | | GA | | 3-0 | 32-42-11 | D02032 | | 3 | | GD01656 | ST.. | E | *2 | 115-199 |
| 0055 | 18 | | GA | | 2-6 | 32-42-11 | D02036 | | 3 | | GD01656 | ST.. | E | *2 | 001-099 |
| 0055 | 18 | | GA | | 3-0 | 32-42-11 | D02036 | | 3 | | GD01656 | ST.. | E | *2 | 115-199 |
| 0061 | 18 | | GA | | 0-8 | 29-32-41 | SM00001 | | 9 | | D04724 | B | | | 001-099 |
| 0061 | 18 | | GA | | 0-6 | 29-32-41 | SM00001 | | 9 | | D04724 | B | | | 115-199 |
| 0063 | 18 | | GA | | 1-11 | 29-35-11 | D00530 | | 2 | 18 | GD00891 | DC.. | E | | 001-099 |
| 0063 | 18 | | GA | | 2-0 | 29-35-11 | D00530 | | 2 | 18 | GD00891 | DC.. | E | | 115-199 |
| 0070 | 18 | | GA | | 1-11 | 32-42-12 | D02672 | | 2 | | GD00896 | DC.. | E | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2412 | 286N2412 | | | LEFT WHEEL WELL- ANTI-SKID AND HYDRAULICS (continued) | | | | | | | | | | | |
| 0070 | 18 | GA | | | 3-0 | 32-42-12 | D02672 | 2 | | | GD00896 | DC.. | E | | 115-199 |
| 0071 | 18 | GA | | | 2-1 | 32-42-11 | D02030 | 2 | | | GD00070 | DC.. | E | | 001-099 |
| 0071 | 18 | GA | | | 3-0 | 32-42-11 | D02030 | 2 | | | GD00070 | DC.. | E | | 115-199 |
| 0072 | 18 | GA | | | 2-4 | 32-42-11 | D02028 | 2 | | | GD00070 | DC.. | E | | 001-099 |
| 0072 | 18 | GA | | | 3-0 | 32-42-11 | D02028 | 2 | | | GD00070 | DC.. | E | | 115-199 |
| 1001 | 18 | GE | CD | | 10-0 | 32-42-11 | D42189P | 1 | | | D02038 | 1 | | | ALL |
| 1001Z | | | CD | | 0-0 | 32-42-11 | D42189P | S/R | | | D02038 | | | AC | ALL |
| 1002 | 18 | GE | CC | | 4-11 | 29-32-41 | SM00001 | | 9 | | GD00891 | DC.. | E | *1 | 001-099 |
| 1002 | 18 | GE | CC | | 5-0 | 29-32-41 | SM00001 | | 9 | | GD00891 | DC.. | E | *1 | 115-199 |
| 1002Z | | | CC | | 0-0 | 29-32-41 | SM00REF | 1 | | AP | GD00891 | DC.. | E | *1 | ALL |
| 1003 | 18 | GE | AE | | 9-9 | 32-42-11 | D42189P | 2 | | | D02036 | 1 | | | 001-099 |
| 1003 | 18 | GE | AE | | 10-0 | 32-42-11 | D42189P | 2 | | | D02036 | 1 | | | 115-199 |
| 1003Z | | | AE | | 0-0 | 32-42-11 | D42189P | S/R | | | D02036 | | | AD | ALL |
| 1005 | 18 | GE | AG | | 9-8 | 32-42-11 | D42189P | 3 | | | D02034 | 1 | | | 001-099 |
| 1005 | 18 | GE | AG | | 10-0 | 32-42-11 | D42189P | 3 | | | D02034 | 1 | | | 115-199 |
| 1005Z | | | AG | | 0-0 | 32-42-11 | D42189P | S/R | | | D02034 | | | AE | ALL |
| 1006 | 18 | GE | AH | | 2-7 | 32-42-11 | D02032 | 2 | | | GD00892 | DC.. | E | *1 | 001-099 |
| 1006 | 18 | GE | AH | | 3-0 | 32-42-11 | D02032 | 2 | | | GD00892 | DC.. | E | *1 | 115-199 |
| 1006Z | | | AH | | 0-0 | 32-42-11 | D02032 | | | AF | GD00892 | DC.. | E | *1 | ALL |
| 1007 | 18 | GE | AI | | 9-5 | 32-42-11 | D42189P | 4 | | | D02032 | 1 | | | 001-099 |
| 1007 | 18 | GE | AI | | 10-0 | 32-42-11 | D42189P | 4 | | | D02032 | 1 | | | 115-199 |
| 1007Z | | | AI | | 0-0 | 32-42-11 | D42189P | S/R | | | D02032 | | | AF | ALL |
| 1008 | 18 | GE | AJ | | 3-1 | 32-42-11 | D02038 | 2 | | | GD00892 | DC.. | E | *2 | 001-099 |
| 1008 | 18 | GE | AJ | | 4-0 | 32-42-11 | D02038 | 2 | | | GD00892 | DC.. | E | *2 | 115-199 |
| 1008Z | | | AJ | | 0-0 | 32-42-11 | D02038 | | | AC | GD00892 | DC.. | E | *2 | ALL |
| 1009 | 18 | GE | AK | | 6-10 | 32-42-11 | D41812P | 11 | 18 | | D02030 | 1 | | | 001-099 |
| 1009 | 18 | GE | AK | | 7-0 | 32-42-11 | D41812P | 11 | 18 | | D02030 | 1 | | | 115-199 |
| 1009Z | | | AK | | 0-0 | 32-42-11 | D41812P | S/R | | | D02030 | | | AG | ALL |
| 1010 | 18 | GE | AL | | 2-11 | 32-42-11 | D02036 | 2 | | | GD00892 | DC.. | E | *3 | 001-099 |
| 1010 | 18 | GE | AL | | 4-0 | 32-42-11 | D02036 | 2 | | | GD00892 | DC.. | E | *3 | 115-199 |
| 1010Z | | | AL | | 0-0 | 32-42-11 | D02036 | | | AD | GD00892 | DC.. | E | *3 | ALL |
| 1011 | 18 | GE | AM | | 7-1 | 32-42-11 | D41812P | 9 | 18 | | D02028 | 1 | | | 001-099 |
| 1011 | 18 | GE | AM | | 7-0 | 32-42-11 | D41812P | 9 | 18 | | D02028 | 1 | | | 115-199 |
| 1011Z | | | AM | | 0-0 | 32-42-11 | D41812P | S/R | | | D02028 | | | AH | ALL |
| 1012 | 18 | GE | AN | | 2-9 | 32-42-11 | D02034 | 2 | | | GD00892 | DC.. | E | *4 | 001-099 |
| 1012 | 18 | GE | AN | | 4-0 | 32-42-11 | D02034 | 2 | | | GD00892 | DC.. | E | *4 | 115-199 |
| 1012Z | | | AN | | 0-0 | 32-42-11 | D02034 | | | AE | GD00892 | DC.. | E | *4 | ALL |
| 1013 | 18 | GE | BB | | 14-8 | 32-42-12 | D42189P | 7 | | | D02672 | 1 | | | 001-099 |
| 1013 | 18 | GE | BB | | 15-0 | 32-42-12 | D42189P | 7 | | | D02672 | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2412 | 286N2412 | | | LEFT WHEEL WELL- ANTI-SKID AND HYDRAULICS (continued) | | | | | | | | | | | |
| 1013Z | | | | BB | 0-0 | 32-42-12 | D42189P | S/R | | | D02672 | | | AA | ALL |
| 1019 | 18 | GE | BD | | 12-7 | 32-42-12 | D42189P | 8 | | | D02674 | 1 | | | 001-099 |
| 1019 | 18 | GE | BD | | 13-0 | 32-42-12 | D42189P | 8 | | | D02674 | 1 | | | 115-199 |
| 1019Z | | | BD | | 0-0 | 32-42-12 | D42189P | S/R | | | GD00908 | ST.. | E | | ALL |
| 1027 | 18 | GE | DH | | 6-5 | 32-42-12 | D02674 | 2 | | | GD00896 | DC.. | E | *2 | 001-099 |
| 1027 | 18 | GE | DH | | 6-0 | 32-42-12 | D02674 | 2 | | | GD00896 | DC.. | E | *2 | 115-199 |
| 1027Z | | | DH | | 0-0 | 32-42-12 | GD00908 | ST.. | E | | GD00896 | DC.. | E | *2 | ALL |
| 1041 | 20 | GE | CA | | 11-10 | 29-11-12 | D03102 | 3 | | | D40964P | 12 | | | 001-099 |
| 1041 | 20 | GE | CA | | 12-0 | 29-11-12 | D03102 | 3 | | | D40964P | 12 | | | 115-199 |
| 1041Z | | | CA | | 0-0 | 29-11-12 | GD00964 | ST.. | E | | D40964P | S/R | | | ALL |
| 2501B | 20 | 2Z | XA | | 12-11 | 32-42-12 | D41812P | 1 | | | D02668 | 1 | | | 001-099 |
| 2501B | 20 | 2Z | XA | | 13-0 | 32-42-12 | D41812P | 1 | | | D02668 | 1 | | | 115-199 |
| 2501R | 20 | 2Z | XA | | 0-0 | 32-42-12 | D41812P | 2 | | | D02668 | 2 | | | ALL |
| 2501ZI | | | XA | | 0-0 | 32-42-12 | D41812P | 21 | 18 | | D02668 | DED | | | ALL |
| 2501ZO | | | XA | | 0-0 | 32-42-12 | D41812P | S/R | | | GD00908 | ST.. | E | | ALL |
| 2502B | 20 | 2Z | AB | | 15-5 | 32-61-13 | D40964P | 5 | | | SP01974 | | 9 | | 001-099 |
| 2502B | 20 | 2Z | AB | | 16-0 | 32-61-13 | D40964P | 5 | | | SP01974 | | 9 | | 115-199 |
| 2502R | 20 | 2Z | AB | | 0-0 | 32-61-13 | D40964P | 4 | | | SP01972 | | 9 | | ALL |
| 2502ZI | | | AB | | 0-0 | 32-61-13 | D40964P | DED | | | SP01974 | | 9 | | ALL |
| 2502ZO | | | AB | | 0-0 | 32-61-13 | D40964P | S/R | | | GD00060 | ST.. | E | | ALL |
| 2503B | 18 | GF | AC | | 23-1 | 29-32-41 | D40964P | 11 | | | SM00001 | | 9 | | 001-099 |
| 2503B | 18 | GF | AC | | 24-0 | 29-32-41 | D40964P | 11 | | | SM00001 | | 9 | | 115-199 |
| 2503R | 18 | GF | AC | | 0-0 | 29-32-41 | D40964P | 10 | | | D04724 | A | | | ALL |
| 2503Z | | | AC | | 0-0 | 29-32-41 | D40964P | S/R | | | SM00REF | 1 | | AP | ALL |
| 2511B | 20 | 2Z | AA | | 16-3 | 32-61-13 | D40964P | 1 | | | SP01970 | | 9 | | 001-099 |
| 2511B | 20 | 2Z | AA | | 16-0 | 32-61-13 | D40964P | 1 | | | SP01970 | | 9 | | 115-199 |
| 2511R | 20 | 2Z | AA | | 0-0 | 32-61-13 | D40964P | 2 | | | SP01968 | | 9 | | ALL |
| 2511ZI | | | AA | | 0-0 | 32-61-13 | D40964P | DED | | | SP01970 | | 9 | | ALL |
| 2511ZO | | | AA | | 0-0 | 32-61-13 | D40964P | S/R | | | GD02362 | ST.. | E | | ALL |
| 2517B | 18 | GF | BA | | 14-10 | 32-42-12 | D41812P | 4 | 18 | | D02670 | 3 | | | 001-099 |
| 2517B | 18 | GF | BA | | 15-0 | 32-42-12 | D41812P | 4 | 18 | | D02670 | 3 | | | 115-199 |
| 2517R | 18 | GF | BA | | 0-0 | 32-42-12 | D41812P | 3 | 18 | | D02670 | 2 | | | ALL |
| 2517Z | | | BA | | 0-0 | 32-42-12 | D41812P | S/R | | | D02670 | | | AB | ALL |
| 2521B | 18 | GF | BF | | 10-11 | 32-42-12 | D41812P | 8 | 18 | | D02752 | 3 | | | 001-099 |
| 2521B | 18 | GF | BF | | 11-0 | 32-42-12 | D41812P | 8 | 18 | | D02752 | 3 | | | 115-199 |
| 2521R | 18 | GF | BF | | 0-0 | 32-42-12 | D41812P | 7 | 18 | | D02752 | 2 | | | ALL |
| 2521Z | | | BF | | 0-0 | 32-42-12 | D41812P | S/R | | | GD01869 | ST.. | E | | ALL |
| 2526B | 18 | GF | BH | | 21-3 | 29-35-11 | D40964P | 6 | | | D00530 | 4 | 18 | | 001-099 |
| 2526B | 18 | GF | BH | | 22-0 | 29-35-11 | D40964P | 6 | | | D00530 | 4 | 18 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2412 | 286N2412 | | | LEFT WHEEL WELL- ANTI-SKID AND HYDRAULICS (continued) | | | | | | | | | | | |
| 2526R | 18 | GF | BH | | 0-0 | 29-35-11 | D40964P | 3 | | | D00530 | 1 | 18 | | ALL |
| 2526Z | | | BH | | 0-0 | 29-35-11 | D40964P | S/R | | | GD00895 | ST.. | E | | ALL |
| 3501B | 20 | GG | AF | | 7-0 | 29-31-11 | D40964P | 8 | | | D02534 | 2 | | | ALL |
| 3501R | 20 | GG | AF | | 0-0 | 29-31-11 | D40964P | 9 | | | D02534 | 3 | | | ALL |
| 3501Y | 20 | GG | AF | | 0-0 | 29-31-11 | D40964P | 7 | | | D02534 | 1 | | | ALL |
| 3501Z | | | AF | | 0-0 | 29-31-11 | D40964P | S/R | | | GD02597 | ST.. | E | | ALL |
| A-AA | | | | | 0-0 | 32-61-13 | S10076 | RED | | | SP01968 | 9 | | | ALL |
| A-AB | | | | | 0-0 | 32-61-13 | S10076 | BLU | | | SP01970 | 9 | | | ALL |
| A-BA | | | | | 0-0 | 32-61-13 | S10073 | RED | | | SP01972 | 9 | | | ALL |
| A-BB | | | | | 0-0 | 32-61-13 | S10073 | BLU | | | SP01974 | 9 | | | ALL |
| W2414 | 286N2414 | | | LEFT WHEEL WELL -MISC EQUIPMENT | | | | | | | | | | | |
| 0001 | 18 | GA | | | 2-4 | 27-51-51 | D03024 | 3 | | | GD01032 | DC.. | E | | ALL |
| 0002 | 18 | GA | | | 1-9 | 32-12-12 | D02508 | 2 | | | GD02693 | DC.. | E | | ALL |
| 0006 | 18 | GA | | | 2-4 | 27-51-51 | D03024 | 1 | | | GD01032 | DC.. | E | | ALL |
| 0009 | 18 | GA | | | 4-10 | 22-11-12 | D00025 | 19 | | | GD00907 | ST.. | E | | ALL |
| 0010 | 18 | GA | | | 2-9 | 28-42-11 | D01760 | 2 | 18 | | GD00917 | DC.. | E | | ALL |
| 0015 | 18 | GA | | | 1-9 | 27-23-11 | D02918 | 1 | | | GD00912 | DC.. | E | | ALL |
| 0016 | 18 | GA | | | 1-9 | 27-23-11 | D02918 | 9 | | | GD00912 | DC.. | E | | ALL |
| 0021 | 18 | GA | | | 2-2 | 27-51-51 | D03024 | 5 | | | GD01034 | ST.. | E | | ALL |
| 0022 | 18 | GA | | | 0-6 | 27-51-51 | D03024 | 2 | | | SM00007 | 9 | | | ALL |
| 0023 | 18 | GA | | | 0-6 | 27-51-51 | D03024 | 4 | | | SM00007 | 9 | | | ALL |
| 0025 | 18 | GA | | | 2-8 | 28-42-11 | D01760 | 4 | 18 | | GD00915 | ST.. | E | | ALL |
| 0027 | 16 | GA | | | 2-0 | 28-22-11 | D01766 | 4 | | | GD00915 | ST.. | E | | ALL |
| 0032 | 18 | GA | | | 1-7 | 32-12-12 | D02508 | 3 | | | GD01611 | ST.. | E | | ALL |
| 0042 | 20 | GA | | | 1-6 | 27-11-11 | D01874 | 3 | | | GD00830 | ST.. | E | | ALL |
| 1001 | 18 | GE | BX | | 25-2 | 32-12-12 | D02508 | 1 | | | SP00338 | 9 | | | ALL |
| 1001Z | | | BX | | 0-0 | 32-12-12 | GD01611 | ST.. | E | | GD02670 | ST.. | E | | ALL |
| 1002 | 18 | GE | AJ | | 10-11 | 27-51-51 | D40348P | 7 | | | SM00007 | 9 | | | ALL |
| 1002Z | | | AJ | | 0-0 | 27-51-51 | D40348P | S/R | | | GD01034 | ST.. | E | | ALL |
| 1004 | 18 | GE | AP | | 10-11 | 28-42-11 | D01760 | 3 | 18 | | D40348P | 4 | | | ALL |
| 1004Z | | | AP | | 0-0 | 28-42-11 | GD00915 | ST.. | E | | D40348P | S/R | | | ALL |
| 1006 | 20 | GE | AS | | 5-1 | 27-62-11 | D03192 | 5 | | | GD01862 | DC.. | E | *1 | ALL |
| 1006Z | | | AS | | 0-0 | 27-62-11 | D03192 | | | CC | GD01862 | DC.. | E | *1 | ALL |
| 1009 | 20 | GE | AX | | 5-1 | 22-11-12 | D00025 | 17 | | | GD00906 | DC.. | E | *1 | ALL |
| 1009Z | | | AX | | 0-0 | 22-11-12 | GD00894 | ST.. | E | *1 | GD00906 | DC.. | E | *1 | 001-099 |
| 1009Z | | | AX | | 0-0 | 22-11-12 | GD00894 | ST.. | E | | GD00906 | DC.. | E | *1 | 115-199 |
| 1010 | 20 | GE | AY | | 5-1 | 22-11-12 | D00025 | 1 | | | GD00906 | DC.. | E | *2 | ALL |
| 1010Z | | | AY | | 0-0 | 22-11-12 | GD00894 | ST.. | E | *2 | GD00906 | DC.. | E | *2 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|--|------------------------|------------------------|---------------------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W2414 | 286N2414 | LEFT WHEEL WELL -MISC EQUIPMENT (continued) | | | |
| 1010Z | | AY | 0-0 22-11-12 | GD00894 ST.. E | GD00906 DC.. E *2 115-199 |
| 1013 | 18 | GE BB | 5-1 27-62-11 | D03192 2 | GD01862 DC.. E *2 ALL |
| 1013Z | | BB | 0-0 27-62-11 | D03192 CC | GD01862 DC.. E *2 ALL |
| 1021 | 20 | GE AM | 10-7 22-11-12 | D40346P 22 | D00025 18 ALL |
| 1021Z | | AM | 0-0 22-11-12 | D40346P S/R | GD00894 ST.. E *3 001-099 |
| 1021Z | | AM | 0-0 22-11-12 | D40346P S/R | GD00894 ST.. E *1 115-199 |
| 1022 | 20 | GE BJ | 10-7 22-11-12 | D40346P 24 | D00025 2 ALL |
| 1022Z | | BJ | 0-0 22-11-12 | D40346P S/R | GD00894 ST.. E *3 001-099 |
| 1022Z | | BJ | 0-0 22-11-12 | D40346P S/R | GD00894 ST.. E *1 115-199 |
| 2002B | 20 | GB AB | 0-6 22-11-11 | D00025 12 | SM00005 9 ALL |
| 2002R | 20 | GB AB | 0-0 22-11-11 | D00025 13 | SM00006 9 ALL |
| 2003B | 20 | GB AC | 0-6 22-11-11 | D00025 7 | SM00005 9 ALL |
| 2003R | 20 | GB AC | 0-0 22-11-11 | D00025 8 | SM00006 9 ALL |
| 2503B | 20 | GF AK | 26-10 27-62-11 | D03192 1 | D40346P 4 ALL |
| 2503R | 20 | GF AK | 0-0 27-62-11 | D03192 4 | D40346P 26 ALL |
| 2503Z | | AK | 0-0 27-62-11 | D03192 DED | D40346P S/R ALL |
| 2507B | 20 | GF AF | 10-11 27-11-11 | D40346P 27 | D01874 1 ALL |
| 2507R | 20 | GF AF | 0-0 27-11-11 | D40346P 28 | D01874 5 ALL |
| 2507Z | | AF | 0-0 27-11-11 | D40346P S/R | GD00830 ST.. E ALL |
| 2508B | 20 | 2Z AA | 16-0 32-61-13 | D40348P 2 | SP01986 9 ALL |
| 2508R | 20 | 2Z AA | 0-0 32-61-13 | D40348P 1 | SP01984 9 ALL |
| 2508ZI | | AA | 0-0 32-61-13 | D40348P DED | SP01986 9 ALL |
| 2508ZO | | AA | 0-0 32-61-13 | D40348P S/R | GD00002 ST.. E ALL |
| 2511B | 20 | GF AD | 10-7 22-13-11 | D40346P 20 | D00025 5 ALL |
| 2511R | 20 | GF AD | 0-0 22-13-11 | D40346P 17 | D00025 6 ALL |
| 2511Z | | AD | 0-0 22-13-11 | D40346P S/R | GD00894 ST.. E *1 ALL |
| 2512B | 20 | GF AG | 10-7 22-11-11 | D40346P 14 | SM00005 9 ALL |
| 2512R | 20 | GF AG | 0-0 22-11-11 | D40346P 15 | SM00006 9 ALL |
| 2512Z | | AG | 0-0 22-11-11 | D40346P S/R | GD00894 ST.. E *2 ALL |
| 2513B | 20 | 2Z AH | 14-5 32-61-13 | D40348P 10 | SP01990 9 ALL |
| 2513R | 20 | 2Z AH | 0-0 32-61-13 | D40348P 9 | SP01988 9 ALL |
| 2513ZI | | AH | 0-0 32-61-13 | D40348P DED | SP01990 9 ALL |
| 2513ZO | | AH | 0-0 32-61-13 | D40348P S/R | GD01521 ST.. E ALL |
| 3501B | 20 | GG CG | 5-5 29-31-11 | D40346P 25 | D02536 2 ALL |
| 3501R | 20 | GG CG | 0-0 29-31-11 | D40346P 23 | D02536 3 ALL |
| 3501Y | 20 | GG CG | 0-0 29-31-11 | D40346P 18 | D02536 1 ALL |
| 3501Z | | CG | 0-0 29-31-11 | D40346P S/R | GD01519 ST.. E ALL |
| 3502B | 20 | GG AI | 13-9 27-23-11 | D40346P 16 | D02918 10 ALL |
| 3502R | 20 | GG AI | 0-0 27-23-11 | D40346P 6 | D02918 2 ALL |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2414 | 286N2414 | | | LEFT WHEEL WELL -MISC EQUIPMENT (continued) | | | | | | | | | | | |
| 3502Y | 20 | GG | AI | | 0-0 | 27-23-11 | D40346P | 1 | | | D02918 | 3 | | | ALL |
| 3502Z | | | AI | | 0-0 | 27-23-11 | D40346P | S/R | | | GD00912 | DC.. | E | | ALL |
| 3503B | 16 | GG | AE | | 10-3 | 28-22-11 | D01766 | 3 | | | D40348P | 3 | | | ALL |
| 3503R | 16 | GG | AE | | 0-0 | 28-22-11 | D01766 | 1 | | | D40348P | 5 | | | ALL |
| 3503Y | 16 | GG | AE | | 0-0 | 28-22-11 | D01766 | 2 | | | D40348P | 6 | | | ALL |
| 3503Z | | | AE | | 0-0 | 28-22-11 | GD00915 | ST.. | E | | D40348P | S/R | | | ALL |
| 3504B | 20 | GG | CA | | 10-7 | 22-13-11 | D40346P | 9 | | | D00025 | 15 | | | ALL |
| 3504R | 20 | GG | CA | | 0-0 | 22-13-11 | D40346P | 8 | | | D00025 | 14 | | | ALL |
| 3504Y | 20 | GG | CA | | 0-0 | 22-13-11 | D40346P | 10 | | | D00025 | 16 | | | ALL |
| 3504Z | | | CA | | 0-0 | 22-13-11 | D40346P | S/R | | | GD00894 | ST.. | E | *4 | 001-099 |
| 3504Z | | | CA | | 0-0 | 22-13-11 | D40346P | S/R | | | GD00894 | ST.. | E | *2 | 115-199 |
| 3505B | 20 | GG | CB | | 10-7 | 22-13-11 | D40346P | 12 | | | D00025 | 10 | | | ALL |
| 3505R | 20 | GG | CB | | 0-0 | 22-13-11 | D40346P | 11 | | | D00025 | 9 | | | ALL |
| 3505Y | 20 | GG | CB | | 0-0 | 22-13-11 | D40346P | 13 | | | D00025 | 11 | | | ALL |
| 3505Z | | | CB | | 0-0 | 22-13-11 | D40346P | S/R | | | GD00894 | ST.. | E | *4 | 001-099 |
| 3505Z | | | CB | | 0-0 | 22-13-11 | D40346P | S/R | | | GD00894 | ST.. | E | *2 | 115-199 |
| A-AA | | | | | 0-6 | 32-61-13 | S10240 | RED | | | SP01984 | 9 | | | ALL |
| A-AB | | | | | 0-6 | 32-61-13 | S10240 | BLU | | | SP01986 | 9 | | | ALL |
| A-BA | | | | | 0-6 | 32-61-13 | S10242 | RED | | | SP01988 | 9 | | | ALL |
| A-BB | | | | | 0-6 | 32-61-13 | S10242 | BLU | | | SP01990 | 9 | | | ALL |
| W2416 | 286N2416 | | | LEFT WHEEL WELL- STANDBY SYSTEMS + MISC | | | | | | | | | | | |
| 0003 | 18 | GA | | | 2-0 | 28-22-31 | D02144 | 4 | | | GD00067 | DC.. | E | | 001-008 |
| 0003 | 18 | GA | | | 1-11 | 28-22-31 | D07744 | 4 | | | GD00067 | DC.. | E | | 009-099 |
| 0003 | 18 | GA | | | 2-6 | 28-22-31 | D02144 | 4 | | | GD00067 | DC.. | E | | 115-199 |
| 0005 | 18 | GA | | | 3-0 | 29-22-11 | D03140 | 2 | | | GD00924 | DC.. | E | | 001-008 |
| 0005 | 18 | GA | | | 1-9 | 29-22-11 | D03140 | 2 | | | GD00924 | DC.. | E | | 009-099, 115-199 |
| 0008 | 18 | GA | | | 2-0 | 29-33-11 | D02540 | 2 | | | GD01659 | ST.. | E | * | 001-008 |
| 0008 | 18 | GA | | | 1-11 | 29-33-11 | D02540 | 2 | | | GD01659 | ST.. | E | * | 009-099, 115-199 |
| 0015 | 18 | GA | | | 2-0 | 28-22-31 | D02144 | 7 | | | GD00066 | ST.. | E | | 001-008 |
| 0015 | 18 | GA | | | 1-10 | 28-22-31 | D07744 | 7 | | | GD00066 | ST.. | E | | 009-099 |
| 0015 | 18 | GA | | | 2-4 | 28-22-31 | D02144 | 7 | | | GD00066 | ST.. | E | | 115-199 |
| 001TI | | | DA | | 0-0 | 29-33-11 | D41406P | = C1 | | | D02540 | | | AD | ALL |
| 001TO | | | DA | | 0-0 | 29-33-11 | D41406P | S/R | | | GD01659 | ST.. | E | | ALL |
| 001TX | 20 | 4J | DA | | 25-0 | 29-33-11 | D41406P | 1 | | | D02540 | 7 | | | 001-008 |
| 001TX | 20 | 4J | DA | | 24-3 | 29-33-11 | D41406P | 1 | | | D02540 | 7 | | | 009-099 |
| 001TX | 20 | 4J | DA | | 24-2 | 29-33-11 | D41406P | 1 | | | D02540 | 7 | | | 115-199 |
| 0031 | 20 | GA | | | 0-6 | 29-33-11 | D02540 | | | AD | D02540 | 1 | | | 001-008 |
| 0031 | 20 | GA | | | 0-7 | 29-33-11 | D02540 | | | AD | D02540 | 1 | | | 009-099, 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2416 | 286N2416 | | | LEFT WHEEL WELL- STANDBY SYSTEMS + MISC (continued) | | | | | | | | | | | |
| 0032 | 20 | GA | | | 0-6 | 29-33-11 | D02540 | | | AD | D02540 | 6 | | | ALL |
| 0040 | 14 | HA | | | 3-0 | 28-25-11 | D02386 | 3 | | | GD01865 | ST.. | E | | 001-008 |
| 0040 | 14 | HA | | | 2-6 | 28-25-11 | D02386 | 3 | | | GD01865 | ST.. | E | | 009-099 |
| 0040 | 14 | HA | | | 2-9 | 28-25-11 | D02386 | 3 | | | GD01865 | ST.. | E | | 115-199 |
| 0041 | 12 | HA | | | 3-0 | 28-25-11 | D02386 | 2 | | | GD01864 | DC.. | E | | 001-008 |
| 0041 | 12 | HA | | | 2-9 | 28-25-11 | D02386 | 2 | | | GD01864 | DC.. | E | | 009-099 |
| 0041 | 12 | HA | | | 2-6 | 28-25-11 | D02386 | 2 | | | GD01864 | DC.. | E | | 115-199 |
| 0043 | 18 | GA | | | 3-0 | 28-42-21 | D02376 | 2 | 18 | | GD01868 | DC.. | E | | 001-008 |
| 0043 | 18 | GA | | | 2-11 | 28-42-21 | D02376 | 2 | 18 | | GD01868 | DC.. | E | | 009-099 |
| 0043 | 18 | GA | | | 3-1 | 28-42-21 | D02376 | 2 | 18 | | GD01868 | DC.. | E | | 115-199 |
| 0044 | 18 | GA | | | 3-0 | 28-42-21 | D02376 | 4 | 18 | | GD01869 | ST.. | E | | 001-008 |
| 0044 | 18 | GA | | | 2-8 | 28-42-21 | D02376 | 4 | 18 | | GD01869 | ST.. | E | | 009-099 |
| 0044 | 18 | GA | | | 3-2 | 28-42-21 | D02376 | 4 | 18 | | GD01869 | ST.. | E | | 115-199 |
| 1001 | 12 | HE | AB | | 14-0 | 28-25-11 | D02386 | 1 | | | D40350P | 27 | | | 001-008 |
| 1001 | 12 | HE | AB | | 14-4 | 28-25-11 | D02386 | 1 | | | D40350P | 27 | | | 009-099 |
| 1001 | 12 | HE | AB | | 13-3 | 28-25-11 | D02386 | 1 | | | D40350P | 27 | | | 115-199 |
| 1001Z | | | AB | | 0-0 | 28-25-11 | GD00928 | ST.. | E | | D40350P | S/R | | | ALL |
| 1002 | 20 | HE | AC | | 13-0 | 28-25-21 | D40350P | 22 | | | D02382 | 6 | | | 001-008 |
| 1002 | 20 | HE | AC | | 10-4 | 28-25-21 | D40350P | 22 | | | D02382 | 6 | | | 009-099 |
| 1002 | 20 | HE | AC | | 9-9 | 28-25-21 | D40350P | 22 | | | D02382 | 6 | | | 115-199 |
| 1002Z | | | AC | | 0-0 | 28-25-21 | D40350P | S/R | | | GD01867 | ST.. | E | | ALL |
| 1003 | 20 | HE | AD | | 14-0 | 28-42-21 | D02376 | 1 | | | D40350P | 5 | | | 001-008 |
| 1003 | 20 | HE | AD | | 14-7 | 28-42-21 | D02376 | 1 | | | D40350P | 5 | | | 009-099 |
| 1003 | 20 | HE | AD | | 14-2 | 28-42-21 | D02376 | 1 | | | D40350P | 5 | | | 115-199 |
| 1003Z | | | AD | | 0-0 | 28-42-21 | GD00928 | ST.. | E | | D40350P | S/R | | | ALL |
| 1005 | 18 | GE | AI | | 8-0 | 29-22-11 | D03140 | 3 | | | D40350P | 16 | 18 | | 001-008 |
| 1005 | 18 | GE | AI | | 7-4 | 29-22-11 | D03140 | 3 | | | D40350P | 16 | 18 | | 009-099 |
| 1005 | 18 | GE | AI | | 6-11 | 29-22-11 | D03140 | 3 | | | D40350P | 16 | 18 | | 115-199 |
| 1005Z | | | AI | | 0-0 | 29-22-11 | GD01557 | ST.. | E | | D40350P | S/R | | | ALL |
| 1009 | 18 | HE | CK | | 19-0 | 26-17-11 | D02798 | =1 | | | SP00300 | | 9 | | 001-008 |
| 1009 | 18 | HE | CK | | 18-8 | 26-17-11 | D02798 | =1 | | | SP00300 | | 9 | | 009-099 |
| 1009 | 18 | HE | CK | | 16-2 | 26-17-11 | D02798 | =1 | | | SP00300 | | 9 | | 115-199 |
| 1009Z | | | CK | | 0-0 | 26-17-11 | GD01783 | ST.. | E | | GD02670 | ST.. | E | | ALL |
| 1010 | 18 | HE | CB | | 12-0 | 26-17-11 | D41406P | 6 | | | D02796 | =1 | | | 001-008 |
| 1010 | 18 | HE | CB | | 11-4 | 26-17-11 | D41406P | 6 | | | D02796 | =1 | | | 009-099 |
| 1010 | 18 | HE | CB | | 10-9 | 26-17-11 | D41406P | 6 | | | D02796 | =1 | | | 115-199 |
| 1010Z | | | CB | | 0-0 | 26-17-11 | D41406P | S/R | | | GD01783 | ST.. | E | | ALL |
| 1026 | 18 | GE | CG | | 26-0 | 32-12-12 | SP01538 | | 9 | | SP01544 | | 9 | | 001-008 |
| 1026 | 18 | GE | CG | | 25-0 | 32-12-12 | SP01538 | | 9 | | SP01544 | | 9 | | 009-099 |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|-------|-----|---|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2416 | 286N2416 | | | LEFT WHEEL WELL- STANDBY SYSTEMS + MISC (continued) | | | | | | | | | | | |
| 1026 | 18 | GE | CG | 22-7 | 32-12-12 | SP01538 | | | 9 | | SP01544 | | 9 | | 115-199 |
| 1026Z | | | CG | 0-0 | 32-12-12 | GD01794 | ST.. | E | | | GD02362 | ST.. | E | | 001-099 |
| 1026Z | | | CG | 0-0 | 32-12-12 | GD01794 | ST.. | E | | | GD02362 | ST.. | E | * | 115-199 |
| 1027 | 18 | GE | CH | 31-0 | 32-12-12 | SP01542 | | | 9 | | SP00602 | | 9 | | 001-008 |
| 1027 | 18 | GE | CH | 30-7 | 32-12-12 | SP01542 | | | 9 | | SP00602 | | 9 | | 009-099 |
| 1027 | 18 | GE | CH | 28-3 | 32-12-12 | SP01542 | | | 9 | | SP00602 | | 9 | | 115-199 |
| 1027Z | | | CH | 0-0 | 32-12-12 | GD01794 | ST.. | E | | | GD02130 | ST.. | E | | ALL |
| 1028 | 18 | GE | CI | 16-0 | 32-12-12 | L00505 | =P | BK | | | SP00035 | | 9 | | 001-008 |
| 1028 | 18 | GE | CI | 16-4 | 32-12-12 | L00505 | =P | BK | | | SP00035 | | 9 | | 009-099 |
| 1028 | 18 | GE | CI | 16-1 | 32-12-12 | L00505 | =P | BK | | | SP00035 | | 9 | | 115-199 |
| 1028Z | | | CI | 0-0 | 32-12-12 | GD01786 | ST.. | E | | | GD02362 | ST.. | E | | 001-099 |
| 1028Z | | | CI | 0-0 | 32-12-12 | GD01786 | ST.. | E | | | GD02362 | ST.. | E | * | 115-199 |
| 1031 | 18 | HP | HG | 21-0 | 32-12-12 | SP01540 | | | 9 | | SP01090 | | 9 | | 001-008 |
| 1031 | 18 | HP | HG | 20-6 | 32-12-12 | SP01540 | | | 9 | | SP01090 | | 9 | | 009-099 |
| 1031 | 18 | HP | HG | 18-2 | 32-12-12 | SP01540 | | | 9 | | SP01090 | | 9 | | 115-199 |
| 1031Z | | | HG | 0-0 | 32-12-12 | GD01794 | ST.. | E | | | GD01073 | ST.. | E | | ALL |
| 1032 | 18 | HP | HF | 13-0 | 32-12-12 | SP01544 | | | 9 | | SP00053 | | 9 | | 001-008 |
| 1032 | 18 | HP | HF | 12-11 | 32-12-12 | SP01544 | | | 9 | | SP00053 | | 9 | | 009-099, 115-199 |
| 1032Z | | | HF | 0-0 | 32-12-12 | GD02362 | ST.. | E | | *1 | GD01073 | ST.. | E | | ALL |
| 1033 | 18 | HE | AJ | 3-0 | 32-12-12 | L00505 | =G | C | | | GD02395 | DC.. | E | *1 | 001-008 |
| 1033 | 18 | HE | AJ | 2-9 | 32-12-12 | L00505 | =G | C | | | GD02395 | DC.. | E | *1 | 009-099 |
| 1033 | 18 | HE | AJ | 2-10 | 32-12-12 | L00505 | =G | C | | | GD02395 | DC.. | E | *1 | 115-199 |
| 1033Z | | | AJ | 0-0 | 32-12-12 | GD01786 | ST.. | E | | | GD02395 | DC.. | E | *1 | ALL |
| 2501B | 20 | GF | BA | 7-0 | 31-31-51 | D00017 | | D | | | D40350P | | 4 | | 001-008 |
| 2501B | 20 | GF | BA | 7-3 | 31-31-51 | D00017 | | D | | | D40350P | | 4 | | 009-099 |
| 2501B | 20 | GF | BA | 6-9 | 31-31-31 | D00017 | | D | | | D40350P | | 4 | | 115-199 |
| 2501R | 20 | GF | BA | 0-0 | 31-31-31 | D00017 | | C | | | D40350P | | 3 | | 001-008 |
| 2501R | 20 | GF | BA | 0-0 | 31-31-51 | D00017 | | C | | | D40350P | | 3 | | 009-099, 115-199 |
| 2501Z | | | BA | 0-0 | 31-31-51 | D00017 | | | | AC | D40350P | S/R | | | 001-099 |
| 2501Z | | | BA | 0-0 | 31-31-31 | D00017 | | | | AC | D40350P | S/R | | | 115-199 |
| 2502B | 20 | GF | BB | 7-0 | 31-31-31 | D00017 | | F | | | D40350P | | 8 | | 001-008 |
| 2502B | 20 | GF | BB | 7-3 | 31-31-51 | D00017 | | F | | | D40350P | | 8 | | 009-099 |
| 2502B | 20 | GF | BB | 6-9 | 31-31-31 | D00017 | | F | | | D40350P | | 8 | | 115-199 |
| 2502R | 20 | GF | BB | 0-0 | 31-31-31 | D00017 | | E | | | D40350P | | 7 | | 001-008, 115-199 |
| 2502R | 20 | GF | BB | 0-0 | 31-31-51 | D00017 | | E | | | D40350P | | 7 | | 009-099 |
| 2502Z | | | BB | 0-0 | 31-31-31 | D00017 | | | | AC | D40350P | S/R | | | 001-008, 115-199 |
| 2502Z | | | BB | 0-0 | 31-31-51 | D00017 | | | | AC | D40350P | S/R | | | 009-099 |
| 2503B | 20 | GF | BC | 7-0 | 31-31-31 | D00017 | | H | | | D40350P | | 10 | | 001-008 |
| 2503B | 20 | GF | BC | 7-3 | 31-31-51 | D00017 | | H | | | D40350P | | 10 | | 009-099 |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 10

May 17/2006



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



WIRE LIST
D280N032

91-21-11
Section W2410
Page 12
May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2410
Page 13
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|--|----------|---------|-------|-------|------|---------|--------|-------|------|---------|
| | GA | CO | TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type |
| W2418 | 286N2418 | | | LEFT WHEEL WELL- CENTER SYSTEM + MISC. (continued) | | | | | | | | | | |
| 3513Y | 20 | GG | CE | 0-0 | 29-33-11 | D40366P | 8 | | | D02538 | 3 | | | ALL |
| 3513Z | | | CE | 0-0 | 29-33-11 | D40366P | S/R | | | GD01694 | ST.. | E | *1 | ALL |
| T-B | | | | 0-0 | 28-21-23 | R10410 | BLU | | | GD00929 | DC.. | GW | | 010-099 |
| T-R | | | | 0-0 | 28-21-23 | R10410 | RED | | | D02502 | 2 | 16 | * | 010-099 |
| W-B | | | | 0-0 | SPARE | R10410 | CAP | Y | | R10410 | BLU | | | 010-099 |
| W-R | | | | 0-0 | SPARE | R10410 | CAP | Y | | R10410 | RED | | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W2410

Page 14 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2441 | 286N2441 | | | E/E-TO CAPTAIN WHEEL,P10,LEFT AND RIGHT WHEEL WELL DISC CHANNEL L2A | | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 27-61-17 | D00623 | | | 6 | GD00643 | ST.. | 2 | | 001-099 |
| 0001 | 20 | | GA | | 3-0 | 27-61-17 | D00623 | | | 6 | GD00643 | ST.. | 2 | | 115-199 |
| 0002 | 20 | | GA | | 3-0 | 27-61-17 | D00871 | | | 6 | GD00108 | ST.. | 2 | | ALL |
| 2001B | 20 | | GB | AA | 88-0 | 27-61-13 | D41761P | | | 3 | D40573P | | 3 | | 001-099 |
| 2001B | 20 | | GB | AA | 87-0 | 27-61-13 | D41761P | | | 3 | D40573P | | 3 | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 27-61-13 | D41761P | | | 1 | D40573P | | 1 | | ALL |
| 2002B | 20 | | GB | AB | 88-0 | 27-61-13 | D41761P | | | 5 | D40573P | | 5 | | 001-099 |
| 2002B | 20 | | GB | AB | 87-0 | 27-61-13 | D41761P | | | 5 | D40573P | | 5 | | 115-199 |
| 2002R | 20 | | GB | AB | 0-0 | 27-61-13 | D41761P | | | 7 | D40573P | | 7 | | ALL |
| 2003B | 20 | | GB | AC | 88-0 | 27-61-13 | D41761P | | | 8 | D40573P | | 8 | | 001-099 |
| 2003B | 20 | | GB | AC | 87-0 | 27-61-13 | D41761P | | | 8 | D40573P | | 8 | | 115-199 |
| 2003R | 20 | | GB | AC | 0-0 | 27-61-13 | D41761P | | | 9 | D40573P | | 9 | | ALL |
| 2004B | 20 | | GB | AD | 92-0 | 27-61-13 | D41761P | | | 13 | D40575P | | 3 | | ALL |
| 2004R | 20 | | GB | AD | 0-0 | 27-61-13 | D41761P | | | 11 | D40575P | | 1 | | ALL |
| 2005B | 20 | | GB | AE | 92-0 | 27-61-13 | D41761P | | | 15 | D40575P | | 5 | | ALL |
| 2005R | 20 | | GB | AE | 0-0 | 27-61-13 | D41761P | | | 17 | D40575P | | 7 | | ALL |
| 2006B | 20 | | GB | AF | 92-0 | 27-61-13 | D41761P | | | 18 | D40575P | | 8 | | ALL |
| 2006R | 20 | | GB | AF | 0-0 | 27-61-13 | D41761P | | | 19 | D40575P | | 9 | | ALL |
| 2007B | 20 | | GB | AG | 88-0 | SPARE | D41761P | | | 4 | D40573P | | 4 | | 001-099 |
| 2007B | 20 | | GB | AG | 87-0 | SPARE | D41761P | | | 4 | D40573P | | 4 | | 115-199 |
| 2007R | 20 | | GB | AG | 0-0 | SPARE | D41761P | | | 2 | D40573P | | 2 | | ALL |
| 2009B | 22 | | GB | AJ | 29-0 | 27-61-17 | D41761P | | | 22 | D00623 | | 5 | | 001-099 |
| 2009B | 22 | | GB | AJ | 29-0 | 27-61-17 | D41761P | | | 31 | D00623 | | 5 | | 115-199 |
| 2009R | 22 | | GB | AJ | 0-0 | 27-61-17 | D41761P | | | 21 | D00623 | | 3 | | 001-099 |
| 2009R | 22 | | GB | AJ | 0-0 | 27-61-17 | D41761P | | | 32 | D00623 | | 3 | | 115-199 |
| 2010B | 22 | | GB | AK | 29-0 | 27-61-17 | D41761P | | | 24 | D00623 | | 1 | | 001-099 |
| 2010B | 22 | | GB | AK | 29-0 | 27-61-17 | D41761P | | | 34 | D00623 | | 1 | | 115-199 |
| 2010R | 22 | | GB | AK | 0-0 | 27-61-17 | D41761P | | | 23 | D00623 | | 2 | | 001-099 |
| 2010R | 22 | | GB | AK | 0-0 | 27-61-17 | D41761P | | | 33 | D00623 | | 2 | | 115-199 |
| 2011B | 22 | | GB | AL | 34-0 | 27-61-17 | D41761P | | | 26 | D00871 | | 2 | | 001-099 |
| 2011B | 22 | | GB | AL | 34-0 | 27-61-17 | D41761P | | | 36 | D00871 | | 2 | | 115-199 |
| 2011R | 22 | | GB | AL | 0-0 | 27-61-17 | D41761P | | | 25 | D00871 | | 1 | | 001-099 |
| 2011R | 22 | | GB | AL | 0-0 | 27-61-17 | D41761P | | | 35 | D00871 | | 1 | | 115-199 |
| 2012B | 22 | | GB | AM | 34-0 | 27-61-17 | D41761P | | | 28 | D00871 | | 5 | | 001-099 |
| 2012B | 22 | | GB | AM | 34-0 | 27-61-17 | D41761P | | | 38 | D00871 | | 5 | | 115-199 |
| 2012R | 22 | | GB | AM | 0-0 | 27-61-17 | D41761P | | | 27 | D00871 | | 3 | | 001-099 |
| 2012R | 22 | | GB | AM | 0-0 | 27-61-17 | D41761P | | | 37 | D00871 | | 3 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2440

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2443 | 286N2443 | | | E/E-TO F/O WHEEL,P10,LEFT AND RIGHT WING REAR SPAR DISC. CHANNEL R2A | | | | | | | | | | | |
| 0001 | 20 | | GA | | 4-0 | 27-61-15 | D00629 | | 6 | | GD00644 | ST.. | E | | 001-099 |
| 0001 | 20 | | GA | | 2-0 | 27-61-15 | D00629 | | 6 | | GD00644 | ST.. | E | | 115-199 |
| 0002 | 20 | | GA | | 5-0 | 27-61-15 | D00875 | | 6 | | GD00108 | ST.. | 2 | | 001-099 |
| 0002 | 20 | | GA | | 3-0 | 27-61-15 | D00875 | | 6 | | GD00108 | ST.. | 2 | | 115-199 |
| 0003 | 20 | | GA | | 90-0 | 27-51-31 | D40029P | | 3 | | D02920 | | 3 | | ALL |
| 0004 | 20 | | GA | | 90-0 | 27-51-31 | D40029P | | 4 | | D01738 | | 1 | | ALL |
| 0005 | 20 | | GA | | 90-0 | 27-51-31 | D40029P | | 1 | | D02920 | | 5 | | ALL |
| 0006 | 20 | | GA | | 90-0 | 27-51-31 | D40029P | | 2 | | D02920 | | 7 | | ALL |
| 0007 | 18 | | GA | | 3-0 | 27-51-31 | D01738 | | 2 | | GD00897 | DC.. | E | | ALL |
| 0008 | 18 | | GA | | 3-0 | 27-51-31 | D02920 | | 1 | | GD01172 | ST.. | E | | ALL |
| 0009 | 18 | | GA | | 3-0 | 27-51-31 | D02920 | | 2 | | GD00897 | DC.. | E | | ALL |
| 2001B | 20 | | GB | AA | 86-0 | 27-61-14 | D41767P | | 3 | | D40505P | | 3 | | 001-099 |
| 2001B | 20 | | GB | AA | 86-0 | 27-61-14 | D41767P | | 3 | | D40505J | | 3 | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 27-61-14 | D41767P | | 1 | | D40505P | | 1 | | 001-099 |
| 2001R | 20 | | GB | AA | 0-0 | 27-61-14 | D41767P | | 1 | | D40505J | | 1 | | 115-199 |
| 2002B | 20 | | GB | AB | 86-0 | 27-61-14 | D41767P | | 5 | | D40505P | | 5 | | 001-099 |
| 2002B | 20 | | GB | AB | 86-0 | 27-61-14 | D41767P | | 5 | | D40505J | | 5 | | 115-199 |
| 2002R | 20 | | GB | AB | 0-0 | 27-61-14 | D41767P | | 7 | | D40505P | | 7 | | 001-099 |
| 2002R | 20 | | GB | AB | 0-0 | 27-61-14 | D41767P | | 7 | | D40505J | | 7 | | 115-199 |
| 2003B | 20 | | GB | AC | 86-0 | 27-61-14 | D41767P | | 8 | | D40505P | | 8 | | 001-099 |
| 2003B | 20 | | GB | AC | 86-0 | 27-61-14 | D41767P | | 8 | | D40505J | | 8 | | 115-199 |
| 2003R | 20 | | GB | AC | 0-0 | 27-61-14 | D41767P | | 9 | | D40505P | | 9 | | 001-099 |
| 2003R | 20 | | GB | AC | 0-0 | 27-61-14 | D41767P | | 9 | | D40505J | | 9 | | 115-199 |
| 2004B | 20 | | GB | AD | 80-0 | 27-61-14 | D41767P | | 13 | | D40519P | | 3 | | 001-099 |
| 2004B | 20 | | GB | AD | 82-0 | 27-61-14 | D41767P | | 13 | | D40519J | | 3 | | 115-199 |
| 2004R | 20 | | GB | AD | 0-0 | 27-61-14 | D41767P | | 11 | | D40519P | | 1 | | 001-099 |
| 2004R | 20 | | GB | AD | 0-0 | 27-61-14 | D41767P | | 11 | | D40519J | | 1 | | 115-199 |
| 2005B | 20 | | GB | AE | 80-0 | 27-61-14 | D41767P | | 15 | | D40519P | | 5 | | 001-099 |
| 2005B | 20 | | GB | AE | 82-0 | 27-61-14 | D41767P | | 15 | | D40519J | | 5 | | 115-199 |
| 2005R | 20 | | GB | AE | 0-0 | 27-61-14 | D41767P | | 17 | | D40519P | | 7 | | 001-099 |
| 2005R | 20 | | GB | AE | 0-0 | 27-61-14 | D41767P | | 17 | | D40519J | | 7 | | 115-199 |
| 2006B | 20 | | GB | AF | 80-0 | 27-61-14 | D41767P | | 18 | | D40519P | | 8 | | 001-099 |
| 2006B | 20 | | GB | AF | 82-0 | 27-61-14 | D41767P | | 18 | | D40519J | | 8 | | 115-199 |
| 2006R | 20 | | GB | AF | 0-0 | 27-61-14 | D41767P | | 19 | | D40519P | | 9 | | 001-099 |
| 2006R | 20 | | GB | AF | 0-0 | 27-61-14 | D41767P | | 19 | | D40519J | | 9 | | 115-199 |
| 2009B | 22 | | GB | AJ | 39-0 | 27-61-15 | D41767P | | 22 | | D00629 | | 5 | | 001-099 |
| 2009B | 22 | | GB | AJ | 40-0 | 27-61-15 | D41767P | | 31 | | D00629 | | 5 | | 115-199 |
| 2009R | 22 | | GB | AJ | 0-0 | 27-61-15 | D41767P | | 21 | | D00629 | | 3 | | 001-099 |
| 2009R | 22 | | GB | AJ | 0-0 | 27-61-15 | D41767P | | 32 | | D00629 | | 3 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2440

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--|---------|----------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2443 | 286N2443 | | | E/E-TO F/O WHEEL,P10,LEFT AND RIGHT WING REAR SPAR DISC. CHANNEL R2A (continued) | | | | | | | | | | | |
| 2010B | 22 | | GB | AK | 39-0 | 27-61-15 | D41767P | 24 | | | D00629 | 1 | | | 001-099 |
| 2010B | 22 | | GB | AK | 40-0 | 27-61-15 | D41767P | 34 | | | D00629 | 1 | | | 115-199 |
| 2010R | 22 | | GB | AK | 0-0 | 27-61-15 | D41767P | 23 | | | D00629 | 2 | | | 001-099 |
| 2010R | 22 | | GB | AK | 0-0 | 27-61-15 | D41767P | 33 | | | D00629 | 2 | | | 115-199 |
| 2011B | 22 | | GB | AL | 41-0 | 27-61-15 | D41767P | 26 | | | D00875 | 2 | | | 001-099 |
| 2011B | 22 | | GB | AL | 42-0 | 27-61-15 | D41767P | 36 | | | D00875 | 2 | | | 115-199 |
| 2011R | 22 | | GB | AL | 0-0 | 27-61-15 | D41767P | 25 | | | D00875 | 1 | | | 001-099 |
| 2011R | 22 | | GB | AL | 0-0 | 27-61-15 | D41767P | 35 | | | D00875 | 1 | | | 115-199 |
| 2012B | 22 | | GB | AM | 41-0 | 27-61-15 | D41767P | 28 | | | D00875 | 5 | | | 001-099 |
| 2012B | 22 | | GB | AM | 42-0 | 27-61-15 | D41767P | 38 | | | D00875 | 5 | | | 115-199 |
| 2012R | 22 | | GB | AM | 0-0 | 27-61-15 | D41767P | 27 | | | D00875 | 3 | | | 001-099 |
| 2012R | 22 | | GB | AM | 0-0 | 27-61-15 | D41767P | 37 | | | D00875 | 3 | | | 115-199 |
| YAAA | | | | | 0-0 | 27-51-31 | GD01172 | ST.. | E | | GD02751 | ST.. | E | | ALL |
| YAAB | | | | | 0-0 | 27-61-14 | GD02550 | ST.. | E | | D40505P | S/R | | | 001-099 |
| YAAB | | | | | 0-0 | 27-61-14 | GD02550 | ST.. | E | | D40505J | S/R | | | 115-199 |
| YAAC | | | | | 0-0 | 27-61-14 | D40519P | S/R | | | GD02751 | ST.. | E | | 001-099 |
| YAAC | | | | | 0-0 | 27-61-14 | D40519J | S/R | | | GD02751 | ST.. | E | | 115-199 |
| W2445 | 286N2445 | | | E/E-TO F/O WHEEL,P10,LEFT AND RIGHT WING SPAR DISC. CHANNEL R2C | | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 27-61-16 | D00633 | 6 | | | GD00644 | ST.. | E | | 001-099 |
| 0001 | 20 | | GA | | 4-0 | 27-61-16 | D00633 | 6 | | | GD00644 | ST.. | E | | 115-199 |
| 0002 | 20 | | GA | | 6-0 | 27-61-16 | D00879 | 6 | | | GD00108 | ST.. | 2 | | 001-099 |
| 0002 | 20 | | GA | | 5-0 | 27-61-16 | D00879 | 6 | | | GD00108 | ST.. | 2 | | 115-199 |
| 2001B | 20 | | GB | AA | 85-0 | 27-61-15 | D41769P | 3 | | | D40529P | 3 | | | 001-099 |
| 2001B | 20 | | GB | AA | 85-0 | 27-61-15 | D41769P | 3 | | | D40529J | 3 | | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 27-61-15 | D41769P | 1 | | | D40529P | 1 | | | 001-099 |
| 2001R | 20 | | GB | AA | 0-0 | 27-61-15 | D41769P | 1 | | | D40529J | 1 | | | 115-199 |
| 2002B | 20 | | GB | AB | 85-0 | 27-61-15 | D41769P | 5 | | | D40529P | 5 | | | 001-099 |
| 2002B | 20 | | GB | AB | 85-0 | 27-61-15 | D41769P | 5 | | | D40529J | 5 | | | 115-199 |
| 2002R | 20 | | GB | AB | 0-0 | 27-61-15 | D41769P | 7 | | | D40529P | 7 | | | 001-099 |
| 2002R | 20 | | GB | AB | 0-0 | 27-61-15 | D41769P | 7 | | | D40529J | 7 | | | 115-199 |
| 2003B | 20 | | GB | AC | 85-0 | 27-61-15 | D41769P | 8 | | | D40529P | 8 | | | 001-099 |
| 2003B | 20 | | GB | AC | 85-0 | 27-61-15 | D41769P | 8 | | | D40529J | 8 | | | 115-199 |
| 2003R | 20 | | GB | AC | 0-0 | 27-61-15 | D41769P | 9 | | | D40529P | 9 | | | 001-099 |
| 2003R | 20 | | GB | AC | 0-0 | 27-61-15 | D41769P | 9 | | | D40529J | 9 | | | 115-199 |
| 2004B | 20 | | GB | AD | 82-0 | 27-61-15 | D41769P | 13 | | | D40541P | 3 | | | 001-099 |
| 2004B | 20 | | GB | AD | 82-0 | 27-61-15 | D41769P | 13 | | | D40541J | 3 | | | 115-199 |
| 2004R | 20 | | GB | AD | 0-0 | 27-61-15 | D41769P | 11 | | | D40541P | 1 | | | 001-099 |
| 2004R | 20 | | GB | AD | 0-0 | 27-61-15 | D41769P | 11 | | | D40541J | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2440

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2445 | 286N2445 | | | E/E-TO F/O WHEEL,P10,LEFT AND RIGHT WING SPAR DISC. CHANNEL R2C (continued) | | | | | | | | | | | |
| 2005B | 20 | GB | AE | | 82-0 | 27-61-15 | D41769P | | 15 | | D40541P | | 5 | | 001-099 |
| 2005B | 20 | GB | AE | | 82-0 | 27-61-15 | D41769P | | 15 | | D40541J | | 5 | | 115-199 |
| 2005R | 20 | GB | AE | | 0-0 | 27-61-15 | D41769P | | 17 | | D40541P | | 7 | | 001-099 |
| 2005R | 20 | GB | AE | | 0-0 | 27-61-15 | D41769P | | 17 | | D40541J | | 7 | | 115-199 |
| 2006B | 20 | GB | AF | | 82-0 | 27-61-15 | D41769P | | 18 | | D40541P | | 8 | | 001-099 |
| 2006B | 20 | GB | AF | | 82-0 | 27-61-15 | D41769P | | 18 | | D40541J | | 8 | | 115-199 |
| 2006R | 20 | GB | AF | | 0-0 | 27-61-15 | D41769P | | 19 | | D40541P | | 9 | | 001-099 |
| 2006R | 20 | GB | AF | | 0-0 | 27-61-15 | D41769P | | 19 | | D40541J | | 9 | | 115-199 |
| 2009B | 22 | GB | AJ | | 38-0 | 27-61-16 | D41769P | | 22 | | D00633 | | 5 | | 001-099 |
| 2009B | 22 | GB | AJ | | 38-0 | 27-61-16 | D41769P | | 31 | | D00633 | | 5 | | 115-199 |
| 2009R | 22 | GB | AJ | | 0-0 | 27-61-16 | D41769P | | 21 | | D00633 | | 3 | | 001-099 |
| 2009R | 22 | GB | AJ | | 0-0 | 27-61-16 | D41769P | | 32 | | D00633 | | 3 | | 115-199 |
| 2010B | 22 | GB | AK | | 38-0 | 27-61-16 | D41769P | | 24 | | D00633 | | 1 | | 001-099 |
| 2010B | 22 | GB | AK | | 38-0 | 27-61-16 | D41769P | | 34 | | D00633 | | 1 | | 115-199 |
| 2010R | 22 | GB | AK | | 0-0 | 27-61-16 | D41769P | | 23 | | D00633 | | 2 | | 001-099 |
| 2010R | 22 | GB | AK | | 0-0 | 27-61-16 | D41769P | | 33 | | D00633 | | 2 | | 115-199 |
| 2011B | 22 | GB | AL | | 40-0 | 27-61-16 | D41769P | | 26 | | D00879 | | 2 | | 001-099 |
| 2011B | 22 | GB | AL | | 40-0 | 27-61-16 | D41769P | | 36 | | D00879 | | 2 | | 115-199 |
| 2011R | 22 | GB | AL | | 0-0 | 27-61-16 | D41769P | | 25 | | D00879 | | 1 | | 001-099 |
| 2011R | 22 | GB | AL | | 0-0 | 27-61-16 | D41769P | | 35 | | D00879 | | 1 | | 115-199 |
| 2012B | 22 | GB | AM | | 40-0 | 27-61-16 | D41769P | | 28 | | D00879 | | 5 | | 001-099 |
| 2012B | 22 | GB | AM | | 40-0 | 27-61-16 | D41769P | | 38 | | D00879 | | 5 | | 115-199 |
| 2012R | 22 | GB | AM | | 0-0 | 27-61-16 | D41769P | | 27 | | D00879 | | 3 | | 001-099 |
| 2012R | 22 | GB | AM | | 0-0 | 27-61-16 | D41769P | | 37 | | D00879 | | 3 | | 115-199 |
| YAAA | | | | | 0-0 | 27-61-15 | GD02540 | ST.. | E | | D40541P | S/R | | | 001-099 |
| YAAA | | | | | 0-0 | 27-61-15 | GD02540 | ST.. | E | | D40541J | S/R | | | 115-199 |
| YAAB | | | | | 0-0 | 27-61-15 | D40529P | S/R | | | GD02585 | ST.. | E | | 001-099 |
| YAAB | | | | | 0-0 | 27-61-15 | D40529J | S/R | | | GD02585 | ST.. | E | | 115-199 |
| W2447 | 286N2447 | | | E/E-TO F/O WHEEL, P10, LEFT & RIGHT REAR SPARE DISCONNECT CHANNEL R2B | | | | | | | | | | | |
| 0001 | 20 | GA | | | 4-0 | 27-61-14 | D00631 | | 6 | | GD00644 | ST.. | E | | 001-099 |
| 0001 | 20 | GA | | | 3-0 | 27-61-14 | D00631 | | 6 | | GD00644 | ST.. | E | | 115-199 |
| 0002 | 20 | GA | | | 4-0 | 27-61-14 | D00881 | | 6 | | GD00108 | ST.. | 2 | | ALL |
| 2001B | 20 | GB | AA | | 74-0 | 27-61-16 | D41771P | | 3 | | D40543P | | 3 | | 001-099 |
| 2001B | 20 | GB | AA | | 75-0 | 27-61-16 | D41771P | | 3 | | D40543J | | 3 | | 115-199 |
| 2001R | 20 | GB | AA | | 0-0 | 27-61-16 | D41771P | | 1 | | D40543P | | 1 | | 001-099 |
| 2001R | 20 | GB | AA | | 0-0 | 27-61-16 | D41771P | | 1 | | D40543J | | 1 | | 115-199 |
| 2002B | 20 | GB | AB | | 74-0 | 27-61-16 | D41771P | | 5 | | D40543P | | 5 | | 001-099 |
| 2002B | 20 | GB | AB | | 75-0 | 27-61-16 | D41771P | | 5 | | D40543J | | 5 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2440

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|---|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2447 | 286N2447 | | | E/E-TO F/O WHEEL, P10, LEFT & RIGHT REAR SPARE DISCONNECT CHANNEL R2B (continued) | | | | | | | | | | | |
| 2002R | 20 | GB | AB | 0-0 | 27-61-16 | D41771P | 7 | | | D40543P | 7 | | | 001-099 | |
| 2002R | 20 | GB | AB | 0-0 | 27-61-16 | D41771P | 7 | | | D40543J | 7 | | | 115-199 | |
| 2003B | 20 | GB | AC | 74-0 | 27-61-16 | D41771P | 8 | | | D40543P | 8 | | | 001-099 | |
| 2003B | 20 | GB | AC | 75-0 | 27-61-16 | D41771P | 8 | | | D40543J | 8 | | | 115-199 | |
| 2003R | 20 | GB | AC | 0-0 | 27-61-16 | D41771P | 9 | | | D40543P | 9 | | | 001-099 | |
| 2003R | 20 | GB | AC | 0-0 | 27-61-16 | D41771P | 9 | | | D40543J | 9 | | | 115-199 | |
| 2004B | 20 | GB | AE | 61-0 | 27-61-16 | D41771P | 13 | | | D40571P | 3 | | | 001-099 | |
| 2004B | 20 | GB | AE | 61-0 | 27-61-16 | D41771P | 13 | | | D40571J | 3 | | | 115-199 | |
| 2004R | 20 | GB | AE | 0-0 | 27-61-16 | D41771P | 11 | | | D40571P | 1 | | | 001-099 | |
| 2004R | 20 | GB | AE | 0-0 | 27-61-16 | D41771P | 11 | | | D40571J | 1 | | | 115-199 | |
| 2005B | 20 | GB | AF | 61-0 | 27-61-16 | D41771P | 15 | | | D40571P | 5 | | | 001-099 | |
| 2005B | 20 | GB | AF | 61-0 | 27-61-16 | D41771P | 15 | | | D40571J | 5 | | | 115-199 | |
| 2005R | 20 | GB | AF | 0-0 | 27-61-16 | D41771P | 17 | | | D40571P | 7 | | | 001-099 | |
| 2005R | 20 | GB | AF | 0-0 | 27-61-16 | D41771P | 17 | | | D40571J | 7 | | | 115-199 | |
| 2006B | 20 | GB | AG | 61-0 | 27-61-16 | D41771P | 18 | | | D40571P | 8 | | | 001-099 | |
| 2006B | 20 | GB | AG | 61-0 | 27-61-16 | D41771P | 18 | | | D40571J | 8 | | | 115-199 | |
| 2006R | 20 | GB | AG | 0-0 | 27-61-16 | D41771P | 19 | | | D40571P | 9 | | | 001-099 | |
| 2006R | 20 | GB | AG | 0-0 | 27-61-16 | D41771P | 19 | | | D40571J | 9 | | | 115-199 | |
| 2009B | 22 | GB | AI | 38-0 | 27-61-14 | D41771P | 22 | | | D00631 | 5 | | | 001-099 | |
| 2009B | 22 | GB | AI | 37-0 | 27-61-14 | D41771P | 22 | | | D00631 | 5 | | | 115-199 | |
| 2009R | 22 | GB | AI | 0-0 | 27-61-14 | D41771P | 21 | | | D00631 | 3 | | | ALL | |
| 2010B | 22 | GB | AJ | 38-0 | 27-61-14 | D41771P | 24 | | | D00631 | 1 | | | 001-099 | |
| 2010B | 22 | GB | AJ | 37-0 | 27-61-14 | D41771P | 24 | | | D00631 | 1 | | | 115-199 | |
| 2010R | 22 | GB | AJ | 0-0 | 27-61-14 | D41771P | 23 | | | D00631 | 2 | | | ALL | |
| 2011B | 22 | GB | AK | 39-0 | 27-61-14 | D41771P | 26 | | | D00881 | 2 | | | ALL | |
| 2011R | 22 | GB | AK | 0-0 | 27-61-14 | D41771P | 25 | | | D00881 | 1 | | | ALL | |
| 2012B | 22 | GB | AL | 39-0 | 27-61-14 | D41771P | 28 | | | D00881 | 5 | | | ALL | |
| 2012R | 22 | GB | AL | 0-0 | 27-61-14 | D41771P | 27 | | | D00881 | 3 | | | ALL | |
| 2013B | 22 | GB | AM | 37-0 | SPARE | D41771P | 29 | | | D00631 | 11 | | | 001-099 | |
| 2013R | 22 | GB | AM | 0-0 | SPARE | D41771P | 30 | | | D00631 | 12 | | | 001-099 | |
| 2014B | 22 | GB | AN | 39-0 | SPARE | D41771P | 31 | | | D00881 | 11 | | | 001-099 | |
| 2014R | 22 | GB | AN | 0-0 | SPARE | D41771P | 32 | | | D00881 | 12 | | | 001-099 | |
| YAAA | | | | 0-0 | 27-61-16 | D40543P | S/R | | | GD02757 | ST.. | E | | 001-099 | |
| YAAA | | | | 0-0 | 27-61-16 | D40543J | S/R | | | GD02757 | ST.. | E | | 115-199 | |
| YAAB | | | | 0-0 | 27-61-16 | D40571P | S/R | | | GD02604 | ST.. | E | | 001-099 | |
| YAAB | | | | 0-0 | 27-61-16 | D40571J | S/R | | | GD02604 | ST.. | E | | 115-199 | |
| W2449 | 286N2449 | | | E/E-TO CAPTAIN WHEEL,P10,LEFT AND RIGHT WHELL WELL DISC.CHANNEL L2C | | | | | | | | | | | |
| 0001 | 20 | GA | | 5-0 | 27-61-18 | D00627 | 6 | | | GD00643 | ST.. | 2 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2440

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2449 | 286N2449 | | | E/E-TO CAPTAIN WHEEL,P10,LEFT AND RIGHT WHELL WELL DISC.CHANNEL L2C (continued) | | | | | | | | | | | |
| 0001 | 20 | GA | | | 4-0 | 27-61-18 | D00627 | | 6 | | GD00643 | ST.. | 2 | | 115-199 |
| 0002 | 20 | GA | | | 3-0 | 27-61-18 | D00873 | | 6 | | GD00108 | ST.. | 2 | | ALL |
| 2001B | 20 | GB | AA | | 87-0 | 27-61-17 | D41763P | | 3 | | D40577P | | 3 | | ALL |
| 2001R | 20 | GB | AA | | 0-0 | 27-61-17 | D41763P | | 1 | | D40577P | | 1 | | ALL |
| 2002B | 20 | GB | AB | | 87-0 | 27-61-17 | D41763P | | 5 | | D40577P | | 5 | | ALL |
| 2002R | 20 | GB | AB | | 0-0 | 27-61-17 | D41763P | | 7 | | D40577P | | 7 | | ALL |
| 2003B | 20 | GB | AC | | 87-0 | 27-61-17 | D41763P | | 8 | | D40577P | | 8 | | ALL |
| 2003R | 20 | GB | AC | | 0-0 | 27-61-17 | D41763P | | 9 | | D40577P | | 9 | | ALL |
| 2004B | 20 | GB | AD | | 90-0 | 27-61-17 | D41763P | | 13 | | D40579P | | 3 | | ALL |
| 2004R | 20 | GB | AD | | 0-0 | 27-61-17 | D41763P | | 11 | | D40579P | | 1 | | ALL |
| 2005B | 20 | GB | AE | | 90-0 | 27-61-17 | D41763P | | 15 | | D40579P | | 5 | | ALL |
| 2005R | 20 | GB | AE | | 0-0 | 27-61-17 | D41763P | | 17 | | D40579P | | 7 | | ALL |
| 2006B | 20 | GB | AF | | 90-0 | 27-61-17 | D41763P | | 18 | | D40579P | | 8 | | ALL |
| 2006R | 20 | GB | AF | | 0-0 | 27-61-17 | D41763P | | 19 | | D40579P | | 9 | | ALL |
| 2009B | 22 | GB | AJ | | 36-0 | 27-61-18 | D41763P | | 22 | | D00627 | | 5 | | 001-099 |
| 2009B | 22 | GB | AJ | | 37-0 | 27-61-18 | D41763P | | 31 | | D00627 | | 5 | | 115-199 |
| 2009R | 22 | GB | AJ | | 0-0 | 27-61-18 | D41763P | | 21 | | D00627 | | 3 | | 001-099 |
| 2009R | 22 | GB | AJ | | 0-0 | 27-61-18 | D41763P | | 32 | | D00627 | | 3 | | 115-199 |
| 2010B | 22 | GB | AK | | 36-0 | 27-61-18 | D41763P | | 24 | | D00627 | | 1 | | 001-099 |
| 2010B | 22 | GB | AK | | 37-0 | 27-61-18 | D41763P | | 34 | | D00627 | | 1 | | 115-199 |
| 2010R | 22 | GB | AK | | 0-0 | 27-61-18 | D41763P | | 23 | | D00627 | | 2 | | 001-099 |
| 2010R | 22 | GB | AK | | 0-0 | 27-61-18 | D41763P | | 33 | | D00627 | | 2 | | 115-199 |
| 2011B | 22 | GB | AL | | 36-0 | 27-61-18 | D41763P | | 26 | | D00873 | | 2 | | 001-099 |
| 2011B | 22 | GB | AL | | 37-0 | 27-61-18 | D41763P | | 36 | | D00873 | | 2 | | 115-199 |
| 2011R | 22 | GB | AL | | 0-0 | 27-61-18 | D41763P | | 25 | | D00873 | | 1 | | 001-099 |
| 2011R | 22 | GB | AL | | 0-0 | 27-61-18 | D41763P | | 35 | | D00873 | | 1 | | 115-199 |
| 2012B | 22 | GB | AM | | 36-0 | 27-61-18 | D41763P | | 28 | | D00873 | | 5 | | 001-099 |
| 2012B | 22 | GB | AM | | 37-0 | 27-61-18 | D41763P | | 38 | | D00873 | | 5 | | 115-199 |
| 2012R | 22 | GB | AM | | 0-0 | 27-61-18 | D41763P | | 27 | | D00873 | | 3 | | 001-099 |
| 2012R | 22 | GB | AM | | 0-0 | 27-61-18 | D41763P | | 37 | | D00873 | | 3 | | 115-199 |

WIRE LIST

D280N032

91-21-11
Section W2440
Page 6 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2451 | 286N2451 | | | E/E-TO CAPTAIN WHEEL,P10,LEFT & RIGHT WHEEL DISCONNECT-CHANNEL L2B | | | | | | | | | | | |
| 0001 | 20 | | GA | | 3-0 | 27-61-13 | D00625 | | 6 | | GD00643 | ST.. | 2 | | ALL |
| 0002 | 20 | | GA | | 5-0 | 27-61-13 | D00877 | | 6 | | GD00108 | ST.. | 2 | | 001-099 |
| 0002 | 20 | | GA | | 7-0 | 27-61-13 | D00877 | | 6 | | GD00108 | ST.. | 2 | | 115-199 |
| 2001B | 20 | | GB | AA | 91-0 | 27-61-18 | D41765P | | 3 | | D40581P | | 3 | | 001-099 |
| 2001B | 20 | | GB | AA | 92-0 | 27-61-18 | D41765P | | 3 | | D40581P | | 3 | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 27-61-18 | D41765P | | 1 | | D40581P | | 1 | | ALL |
| 2002B | 20 | | GB | AB | 91-0 | 27-61-18 | D41765P | | 5 | | D40581P | | 5 | | 001-099 |
| 2002B | 20 | | GB | AB | 92-0 | 27-61-18 | D41765P | | 5 | | D40581P | | 5 | | 115-199 |
| 2002R | 20 | | GB | AB | 0-0 | 27-61-18 | D41765P | | 7 | | D40581P | | 7 | | ALL |
| 2003B | 20 | | GB | AC | 91-0 | 27-61-18 | D41765P | | 8 | | D40581P | | 8 | | 001-099 |
| 2003B | 20 | | GB | AC | 92-0 | 27-61-18 | D41765P | | 8 | | D40581P | | 8 | | 115-199 |
| 2003R | 20 | | GB | AC | 0-0 | 27-61-18 | D41765P | | 9 | | D40581P | | 9 | | ALL |
| 2004B | 20 | | GB | AD | 97-0 | 27-61-18 | D41765P | | 13 | | D40591P | | 3 | | 001-099 |
| 2004B | 20 | | GB | AD | 95-0 | 27-61-18 | D41765P | | 13 | | D40591P | | 3 | | 115-199 |
| 2004R | 20 | | GB | AD | 0-0 | 27-61-18 | D41765P | | 11 | | D40591P | | 1 | | ALL |
| 2005B | 20 | | GB | AE | 97-0 | 27-61-18 | D41765P | | 15 | | D40591P | | 5 | | 001-099 |
| 2005B | 20 | | GB | AE | 95-0 | 27-61-18 | D41765P | | 15 | | D40591P | | 5 | | 115-199 |
| 2005R | 20 | | GB | AE | 0-0 | 27-61-18 | D41765P | | 17 | | D40591P | | 7 | | ALL |
| 2006B | 20 | | GB | AF | 97-0 | 27-61-18 | D41765P | | 18 | | D40591P | | 8 | | 001-099 |
| 2006B | 20 | | GB | AF | 95-0 | 27-61-18 | D41765P | | 18 | | D40591P | | 8 | | 115-199 |
| 2006R | 20 | | GB | AF | 0-0 | 27-61-18 | D41765P | | 19 | | D40591P | | 9 | | ALL |
| 2009B | 22 | | GB | AI | 40-0 | 27-61-13 | D41765P | | 22 | | D00625 | | 5 | | ALL |
| 2009R | 22 | | GB | AI | 0-0 | 27-61-13 | D41765P | | 21 | | D00625 | | 3 | | ALL |
| 2010B | 22 | | GB | AJ | 40-0 | 27-61-13 | D41765P | | 24 | | D00625 | | 1 | | ALL |
| 2010R | 22 | | GB | AJ | 0-0 | 27-61-13 | D41765P | | 23 | | D00625 | | 2 | | ALL |
| 2011B | 22 | | GB | AK | 39-0 | 27-61-13 | D41765P | | 26 | | D00877 | | 2 | | 001-099 |
| 2011B | 22 | | GB | AK | 40-0 | 27-61-13 | D41765P | | 26 | | D00877 | | 2 | | 115-199 |
| 2011R | 22 | | GB | AK | 0-0 | 27-61-13 | D41765P | | 25 | | D00877 | | 1 | | ALL |
| 2012B | 22 | | GB | AL | 39-0 | 27-61-13 | D41765P | | 28 | | D00877 | | 5 | | 001-099 |
| 2012B | 22 | | GB | AL | 40-0 | 27-61-13 | D41765P | | 28 | | D00877 | | 5 | | 115-199 |
| 2012R | 22 | | GB | AL | 0-0 | 27-61-13 | D41765P | | 27 | | D00877 | | 3 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2450

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2502 | 286N2502 | | | AD0880 TO AIR SUPPLY ISOLATION VALVE AND DUCT LEAK DETECTION | | | | | | | | | | | |
| 1028 | 18 | HP | BU | | 17-0 | 26-18-21 | D41116P | 5 | | | D01998 | = 1 | | | ALL |
| 1028Z | | | BU | | 0-0 | 26-18-21 | D41116P | S/R | | | GD00288 | ST.. | E | | ALL |
| 1029 | 18 | HP | BV | | 8-0 | 26-18-21 | D41116P | 6 | | | D01996 | = 1 | | | ALL |
| 1029Z | | | BV | | 0-0 | 26-18-21 | D41116P | S/R | | | GD03690 | ST.. | E | | ALL |
| 1030 | 18 | HP | BW | | 17-0 | 26-18-21 | D41116P | 7 | | | D01994 | = 1 | | | ALL |
| 1030Z | | | BW | | 0-0 | 26-18-21 | D41116P | S/R | | | GD00288 | ST.. | E | | ALL |
| 1031 | 18 | HP | BX | | 8-0 | 26-18-21 | D41116P | 8 | | | D02026 | = 1 | | | ALL |
| 1031Z | | | BX | | 0-0 | 26-18-21 | D41116P | S/R | | | GD03690 | ST.. | E | | ALL |
| 1032 | 20 | HP | CE | | 5-0 | 36-11-31 | GD02181 | AC.. | E | * | D01604 | 3 | | | 001-008 |
| 1032 | 20 | HP | CE | | 6-0 | 36-11-31 | GD02181 | AC.. | E | * | D07814 | 3 | | | 009-099 |
| 1032 | 20 | HP | CE | | 6-0 | 36-11-31 | GD02181 | AC.. | E | * | D01604 | 3 | | | 115-199 |
| 1032Z | | | CE | | 0-0 | 36-11-31 | GD02181 | AC.. | E | * | GD00286 | ST.. | E | | ALL |
| 2505B | 20 | GF | CJ | | 5-0 | 36-11-31 | GD02321 | DC.. | E | *1 | D01604 | 6 | | | 001-008 |
| 2505B | 20 | GF | CJ | | 6-0 | 36-11-31 | GD02321 | DC.. | E | *1 | D07814 | 6 | | | 009-099 |
| 2505B | 20 | GF | CJ | | 6-0 | 36-11-31 | GD02321 | DC.. | E | *1 | D01604 | 6 | | | 115-199 |
| 2505R | 20 | GF | CJ | | 0-0 | 36-11-31 | GD02321 | DC.. | E | *1 | D01604 | 5 | | | 001-008, 115-199 |
| 2505R | 20 | GF | CJ | | 0-0 | 36-11-31 | GD02321 | DC.. | E | *1 | D07814 | 5 | | | 009-099 |
| 2505Z | | | CJ | | 0-0 | 36-11-31 | GD02321 | DC.. | E | *1 | GD00286 | ST.. | E | * | ALL |
| 4501B | 20 | GH | CH | | 6-0 | 36-11-31 | D41116P | 1 | | | D01604 | 4 | | | 001-008, 115-199 |
| 4501B | 20 | GH | CH | | 9-0 | 36-11-31 | D41116P | 1 | | | D07814 | 4 | | | 009-099 |
| 4501G | 20 | GH | CH | | 0-0 | 36-11-31 | D41116P | 3 | | | D01604 | 2 | | | 001-008, 115-199 |
| 4501G | 20 | GH | CH | | 0-0 | 36-11-31 | D41116P | 3 | | | D07814 | 2 | | | 009-099 |
| 4501R | 20 | GH | CH | | 0-0 | 36-11-31 | D41116P | 2 | | | D01604 | 1 | | | 001-008, 115-199 |
| 4501R | 20 | GH | CH | | 0-0 | 36-11-31 | D41116P | 2 | | | D07814 | 1 | | | 009-099 |
| 4501Y | 20 | GH | CH | | 0-0 | 36-11-31 | D41116P | 4 | | | D01604 | 7 | | | 001-008, 115-199 |
| 4501Y | 20 | GH | CH | | 0-0 | 36-11-31 | D41116P | 4 | | | D07814 | 7 | | | 009-099 |
| 4501Z | | | CH | | 0-0 | 36-11-31 | D41116P | S/R | | | GD00286 | ST.. | E | * | ALL |
| W2506 | 286N2506 | | | RIGHT AIR CONDITIONING BAY | | | | | | | | | | | |
| 0001 | 20 | GA | | | 0-6 | 36-21-11 | D01608 | 3 | | | SM00009 | | 9 | | 115-199 |
| 0003 | 20 | GA | | | 1-7 | 36-21-11 | D04660 | 5 | | | GD02264 | ST.. | E | | 001-099 |
| 0003 | 20 | GA | | | 3-1 | 36-21-11 | D01608 | 5 | | | GD01896 | ST.. | E | *1 | 115-199 |
| 0020 | 20 | GA | | | 2-6 | 21-51-21 | D01932 | 2 | | | GD01876 | ST.. | E | | ALL |
| 0024 | 20 | GA | | | 2-6 | 21-51-21 | D01934 | 2 | | | GD01876 | ST.. | E | *3 | ALL |
| 0037 | 20 | GA | | | 2-5 | 21-51-23 | D03000 | 19 | | | GD00691 | ST.. | E | | ALL |
| 0045 | 20 | GA | | | 1-5 | 21-51-23 | D03002 | 19 | | | GD02034 | ST.. | E | *1 | ALL |
| 0053 | 20 | GA | | | 1-5 | 21-51-23 | D03014 | 13 | | | GD00228 | ST.. | E | | ALL |
| 0073 | 18 | GA | | | 1-10 | 33-44-11 | D00038 | 2 | | | GD00935 | AC.. | E | | ALL |
| 0075 | 20 | GA | | | 1-9 | 21-51-24 | D04058 | 2 | | | GD00257 | ST.. | E | *1 | ALL |

WIRE LIST

D280N032

91-21-11

Section W2500

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | Effectivity | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|-------------|------|---------|--|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice | |
| W2506 | 286N2506 | | | RIGHT AIR CONDITIONING BAY (continued) | | | | | | | | | | | | |
| 0086 | 20 | GA | | | 1-8 | 36-11-22 | GD01896 | ST.. | E | *2 | D02692 | 6 | | | ALL | |
| 0089 | 20 | GA | | | 1-3 | 21-52-31 | GD03150 | ST.. | E | | D04644 | 12 | | | ALL | |
| 0090 | 20 | GA | | | 1-7 | 36-21-11 | GD02264 | ST.. | E | | D04660 | 5 | | | 115-199 | |
| 0107 | 20 | GA | | | 3-5 | 21-51-22 | D04236 | 2 | | | GD01876 | ST.. | E | *2 | ALL | |
| 0109 | 18 | GA | | | 1-10 | 33-44-11 | D00038 | 3 | | | GD00934 | ST.. | E | | ALL | |
| 1001 | 20 | GE | CA | | 5-0 | 36-21-11 | SM00009 | | 9 | | D04660 | 3 | | | 115-199 | |
| 1001Z | | | CA | | 0-0 | 36-21-11 | SM00REF | 9 | | AA | GD02264 | ST.. | E | | 115-199 | |
| 1002 | 18 | GE | CU | | 17-3 | 33-31-21 | SP01574 | | 9 | | GD00689 | DC.. | E | * | 001-099 | |
| 1002 | 18 | GE | CU | | 17-3 | 33-31-21 | SP01574 | | 9 | | GD00689 | DC.. | E | | 115-199 | |
| 1002Z | | | CU | | 0-0 | 33-31-21 | GD00258 | ST.. | E | | GD00689 | DC.. | E | * | 001-099 | |
| 1002Z | | | CU | | 0-0 | 33-31-21 | GD00258 | ST.. | E | | GD00689 | DC.. | E | | 115-199 | |
| 1003 | 20 | GE | AW | | 10-6 | 30-71-11 | D40070P | 22 | | | SP00326 | 9 | | | ALL | |
| 1003Z | | | AW | | 0-0 | 30-71-11 | D40070P | S/R | | | GD01927 | ST.. | E | | ALL | |
| 1009 | 18 | GE | BW | | 17-7 | 33-31-21 | SP00318 | | 9 | | S00362 | 3 | C | | ALL | |
| 1009Z | | | BW | | 0-0 | 33-31-21 | GD00258 | ST.. | E | | GD00217 | ST.. | E | | ALL | |
| 1010 | 20 | GE | BX | | 4-11 | 36-21-11 | D04660 | 3 | | | D40068P | 45 | | | 001-099 | |
| 1010 | 20 | GE | BX | | 6-0 | 36-21-11 | SM00009 | | 9 | | D40068P | 45 | | | 115-199 | |
| 1010Z | | | BX | | 0-0 | 36-21-11 | D40068P | S/R | | | GD02264 | ST.. | E | | 001-099 | |
| 1010Z | | | BX | | 0-0 | 36-21-11 | SM00REF | 9 | | AA | D40068P | S/R | | | 115-199 | |
| 1011 | 18 | GE | AS | | 3-9 | 33-31-21 | S00362 | 2 | C | | S00361 | 2 | C | | 001-099 | |
| 1011Z | | | AS | | 0-0 | 33-31-21 | GD00217 | ST.. | E | | GD01196 | ST.. | E | | 001-099 | |
| 1012 | 20 | GE | CB | | 1-7 | 36-21-11 | D04660 | 4 | | | GD02321 | DC.. | E | *3 | 001-099 | |
| 1012 | 20 | GE | CB | | 4-6 | 36-21-11 | D01608 | 4 | | | GD02321 | DC.. | E | *3 | 115-199 | |
| 1012Z | | | CB | | 0-0 | 36-21-11 | GD02264 | ST.. | E | | GD02321 | DC.. | E | *3 | 001-099 | |
| 1012Z | | | CB | | 0-0 | 36-21-11 | GD01896 | ST.. | E | *1 | GD02321 | DC.. | E | *3 | 115-199 | |
| 1013 | 18 | GE | CF | | 24-5 | 33-44-11 | D00038 | 1 | | | D41102P | 9 | 18 | | 001-099 | |
| 1013 | 18 | GE | CF | | 24-7 | 33-44-11 | D00038 | 1 | | | D41102P | 9 | 18 | | 115-199 | |
| 1013Z | | | CF | | 0-0 | 33-44-11 | GD00934 | ST.. | E | | D41102P | S/R | | | ALL | |
| 1014 | 20 | GE | BO | | 10-8 | 21-51-25 | D03030 | 1 | | | D41102P | 10 | | | 001-099 | |
| 1014 | 20 | GE | BO | | 10-9 | 21-51-25 | D03030 | 1 | | | D41102P | 10 | | | 115-199 | |
| 1014Z | | | BO | | 0-0 | 21-51-25 | GD02066 | ST.. | E | | D41102P | S/R | | | ALL | |
| 1015 | 20 | GE | AN | | 13-5 | 21-51-25 | D03030 | 2 | | | GD02803 | DC.. | E | *1 | ALL | |
| 1015Z | | | AN | | 0-0 | 21-51-25 | GD02066 | ST.. | E | | GD02803 | DC.. | E | *1 | ALL | |
| 1016 | 20 | GE | BS | | 15-4 | 21-51-25 | D04098 | 1 | | | D41102P | 11 | | | 001-099 | |
| 1016 | 20 | GE | BS | | 15-5 | 21-51-25 | D04098 | 1 | | | D41102P | 11 | | | 115-199 | |
| 1016Z | | | BS | | 0-0 | 21-51-25 | GD02188 | ST.. | E | | D41102P | S/R | | | ALL | |
| 1017 | 20 | GE | AO | | 7-4 | 21-51-25 | D04098 | 2 | | | GD02839 | DC.. | E | *2 | ALL | |
| 1017Z | | | AO | | 0-0 | 21-51-25 | GD02188 | ST.. | E | | GD02839 | DC.. | E | *2 | ALL | |
| 1018 | 20 | GE | BE | | 9-8 | 21-51-21 | D01936 | 2 | | | D40068P | 21 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2500

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2506 | 286N2506 | | | RIGHT AIR CONDITIONING BAY (continued) | | | | | | | | | | | |
| 1018 | 20 | GE | BE | | 10-9 | 21-51-21 | D01936 | 2 | 18 | | D40068P | 21 | 18 | | 115-199 |
| 1018Z | | | BE | | 0-0 | 21-51-21 | GD00218 | ST.. | E | | D40068P | S/R | | | ALL |
| 1019 | 20 | GE | AP | | 10-9 | 21-51-21 | D01936 | 1 | | | GD02803 | DC.. | E | *2 | ALL |
| 1019Z | | | AP | | 0-0 | 21-51-21 | GD00218 | ST.. | E | | GD02803 | DC.. | E | *2 | ALL |
| 1020 | 20 | GE | AY | | 9-8 | 21-51-21 | D01932 | 1 | | | D40068P | 1 | | | 001-099 |
| 1020 | 20 | GE | AY | | 10-9 | 21-51-21 | D01932 | 1 | | | D40068P | 1 | | | 115-199 |
| 1020Z | | | AY | | 0-0 | 21-51-21 | GD01876 | ST.. | E | *1 | D40068P | S/R | | | ALL |
| 1021 | 20 | GE | AQ | | 12-10 | 21-51-21 | D01932 | 3 | | | GD02833 | DC.. | E | *1 | ALL |
| 1021Z | | | AQ | | 0-0 | 21-51-21 | GD01876 | ST.. | E | *1 | GD02833 | DC.. | E | *1 | ALL |
| 1024 | 20 | GE | AT | | 21-1 | 21-51-23 | D03000 | 1 | | | GD02789 | AC.. | E | *1 | ALL |
| 1024Z | | | AT | | 0-0 | 21-51-23 | GD00691 | ST.. | E | *2 | GD02789 | AC.. | E | *1 | ALL |
| 1025 | 20 | GE | AU | | 22-4 | 21-51-23 | D03002 | 1 | | | GD02791 | AC.. | E | *1 | ALL |
| 1025Z | | | AU | | 0-0 | 21-51-23 | GD02034 | ST.. | E | *3 | GD02791 | AC.. | E | *1 | ALL |
| 1026 | 20 | GE | AV | | 9-4 | 21-51-23 | D03014 | 3 | | | GD02789 | AC.. | E | *2 | ALL |
| 1026Z | | | AV | | 0-0 | 21-51-23 | GD00228 | ST.. | E | *1 | GD02789 | AC.. | E | *2 | ALL |
| 1027 | 18 | GE | AX | | 12-10 | 21-51-21 | D01934 | 3 | 18 | | GD02833 | DC.. | E | *2 | ALL |
| 1027Z | | | AX | | 0-0 | 21-51-21 | GD01876 | ST.. | E | *3 | GD02833 | DC.. | E | *2 | ALL |
| 1044 | 20 | GT | BT | | 4-3 | 36-22-11 | D01560 | 1 | | | D40068P | 51 | | | 001-099 |
| 1044 | 20 | GE | BT | | 5-4 | 36-22-11 | D01560 | 1 | | | D40068P | 5 | | | 115-199 |
| 1044Z | | | BT | | 0-0 | 36-22-11 | GD02226 | ST.. | E | * | D40068P | S/R | | | ALL |
| 1045 | 20 | GT | AJ | | 6-7 | 36-22-11 | D01560 | 2 | | | GD02321 | DC.. | E | *2 | 001-099 |
| 1045 | 20 | GE | AJ | | 6-7 | 36-22-11 | D01560 | 2 | | | GD02321 | DC.. | E | *2 | 115-199 |
| 1045Z | | | AJ | | 0-0 | 36-22-11 | GD02226 | ST.. | E | * | GD02321 | DC.. | E | *2 | ALL |
| 2501B | 20 | GF | BK | | 20-2 | 21-51-23 | D03000 | 3 | | | D41102P | 1 | | | 001-099 |
| 2501B | 20 | GF | BK | | 20-3 | 21-51-23 | D03000 | 3 | | | D41102P | 1 | | | 115-199 |
| 2501R | 20 | GF | BK | | 0-0 | 21-51-23 | D03000 | 2 | | | D41102P | 2 | | | ALL |
| 2501Z | | | BK | | 0-0 | 21-51-23 | GD00691 | ST.. | E | *2 | D41102P | S/R | | | ALL |
| 2502B | 20 | GF | BI | | 5-1 | 36-11-22 | D40068P | 4 | | | D02692 | 3 | | | 001-099 |
| 2502B | 20 | GF | BI | | 6-8 | 36-11-22 | D40068P | 4 | | | D02692 | 3 | | | 115-199 |
| 2502R | 20 | GF | BI | | 0-0 | 36-11-22 | D40068P | 9 | | | D02692 | 2 | | | ALL |
| 2502Z | | | BI | | 0-0 | 36-11-22 | D40068P | S/R | | | GD01896 | ST.. | E | *2 | ALL |
| 2503B | 20 | GF | BM | | 13-4 | 21-51-22 | D03010 | 2 | | | D40068P | 2 | | | 001-099 |
| 2503B | 20 | GF | BM | | 14-5 | 21-51-22 | D03010 | 2 | | | D40068P | 2 | | | 115-199 |
| 2503R | 20 | GF | BM | | 0-0 | 21-51-22 | D03010 | 1 | | | D40068P | 3 | | | ALL |
| 2503Z | | | BM | | 0-0 | 21-51-22 | GD00259 | ST.. | E | | D40068P | S/R | | | ALL |
| 2504B | 20 | GF | BN | | 8-6 | 21-51-23 | D03002 | 3 | | | D41102P | 3 | | | 001-099 |
| 2504B | 20 | GF | BN | | 8-7 | 21-51-23 | D03002 | 3 | | | D41102P | 3 | | | 115-199 |
| 2504R | 20 | GF | BN | | 0-0 | 21-51-23 | D03002 | 2 | | | D41102P | 4 | | | ALL |
| 2504Z | | | BN | | 0-0 | 21-51-23 | GD02034 | ST.. | E | *3 | D41102P | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2500

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|---------|------|--------|-------------|-----|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2506 | 286N2506 | | | RIGHT AIR CONDITIONING BAY (continued) | | | | | | | | | | | | |
| 2505B | 20 | GF | AA | | 4-11 | 36-21-11 | D04660 | | 2 | | D40068P | 47 | | | 001-099 | |
| 2505B | 20 | GF | AA | | 6-11 | 36-21-11 | D01608 | | 2 | | D40068P | 47 | | | 115-199 | |
| 2505R | 20 | GF | AA | | 0-0 | 36-21-11 | D04660 | | 1 | | D40068P | 46 | | | 001-099 | |
| 2505R | 20 | GF | AA | | 0-0 | 36-21-11 | D01608 | | 1 | | D40068P | 46 | | | 115-199 | |
| 2505Z | | | AA | | 0-0 | 36-21-11 | D40068P | | S/R | | GD02264 | ST.. | E | | 001-099 | |
| 2505Z | | | AA | | 0-0 | 36-21-11 | D40068P | | S/R | | GD01896 | ST.. | E | *1 | 115-199 | |
| 2506B | 20 | GF | BP | | 14-4 | 21-51-23 | D03014 | | 1 | | D41102P | 5 | | | 001-099 | |
| 2506B | 20 | GF | BP | | 14-5 | 21-51-23 | D03014 | | 1 | | D41102P | 5 | | | 115-199 | |
| 2506R | 20 | GF | BP | | 0-0 | 21-51-23 | D03014 | | 2 | | D41102P | 6 | | | ALL | |
| 2506Z | | | BP | | 0-0 | 21-51-23 | GD00228 | | ST.. | E | *1 | D41102P | S/R | | ALL | |
| 2507B | 20 | GF | BA | | 10-9 | 21-51-22 | D04236 | | 1 | | D40070P | 4 | | | ALL | |
| 2507R | 20 | GF | BA | | 0-0 | 21-51-22 | D04236 | | 3 | | D40070P | 3 | | | ALL | |
| 2507Z | | | BA | | 0-0 | 21-51-22 | GD01876 | | ST.. | E | *2 | D40070P | S/R | | ALL | |
| 2508B | 18 | GF | AZ | | 9-8 | 21-51-21 | D01934 | | 5 | 18 | | D40068P | 19 | 18 | 001-099 | |
| 2508B | 18 | GF | AZ | | 10-9 | 21-51-21 | D01934 | | 5 | 18 | | D40068P | 19 | 18 | 115-199 | |
| 2508R | 18 | GF | AZ | | 0-0 | 21-51-21 | D01934 | | 1 | 18 | | D40068P | 20 | 18 | ALL | |
| 2508Z | | | AZ | | 0-0 | 21-51-21 | GD01876 | | ST.. | E | *3 | D40068P | S/R | | ALL | |
| 2509B | 20 | GF | BR | | 20-2 | 21-51-23 | D03000 | | 13 | | D41102P | 22 | | | 001-099 | |
| 2509B | 20 | GF | BR | | 20-3 | 21-51-23 | D03000 | | 13 | | D41102P | 22 | | | 115-199 | |
| 2509R | 20 | GF | BR | | 0-0 | 21-51-23 | D03000 | | 16 | | D41102P | 23 | | | ALL | |
| 2509Z | | | BR | | 0-0 | 21-51-23 | GD00691 | | ST.. | E | *1 | D41102P | S/R | | ALL | |
| 2510B | 20 | GF | BQ | | 21-3 | 21-51-23 | D03000 | | 15 | | GD02807 | DC.. | E | *1 | ALL | |
| 2510R | 20 | GF | BQ | | 0-0 | 21-51-23 | D03000 | | 18 | | GD02807 | DC.. | E | *1 | ALL | |
| 2510Z | | | BQ | | 0-0 | 21-51-23 | GD00691 | | ST.. | E | *1 | GD02807 | DC.. | E | *1 | ALL |
| 2511B | 20 | GF | BB | | 15-5 | 21-51-24 | D04056 | | 2 | | D40068P | 48 | | | 001-099 | |
| 2511B | 20 | GF | BB | | 16-6 | 21-51-24 | D04056 | | 2 | | D40068P | 48 | | | 115-199 | |
| 2511R | 20 | GF | BB | | 0-0 | 21-51-24 | D04056 | | 1 | | D40068P | 44 | | | ALL | |
| 2511Z | | | BB | | 0-0 | 21-51-24 | GD00227 | | ST.. | E | | D40068P | S/R | | ALL | |
| 2512B | 20 | GF | AB | | 13-4 | 21-51-24 | D04054 | | 2 | | D40068P | 43 | | | 001-099 | |
| 2512B | 20 | GF | AB | | 14-5 | 21-51-24 | D04054 | | 2 | | D40068P | 43 | | | 115-199 | |
| 2512R | 20 | GF | AB | | 0-0 | 21-51-24 | D04054 | | 1 | | D40068P | 42 | | | ALL | |
| 2512Z | | | AB | | 0-0 | 21-51-24 | GD00259 | | ST.. | E | | D40068P | S/R | | ALL | |
| 2513B | 20 | GF | BC | | 13-7 | 21-51-24 | D04058 | | 1 | | D40068P | 50 | | | 001-099 | |
| 2513B | 20 | GF | BC | | 14-8 | 21-51-24 | D04058 | | 1 | | D40068P | 50 | | | 115-199 | |
| 2513R | 20 | GF | BC | | 0-0 | 21-51-24 | D04058 | | 3 | | D40068P | 49 | | | ALL | |
| 2513Z | | | BC | | 0-0 | 21-51-24 | GD00257 | | ST.. | E | *1 | D40068P | S/R | | ALL | |
| 2514B | 20 | GF | BD | | 14-11 | 21-51-25 | D03028 | | 1 | | D41102P | 12 | | | 001-099 | |
| 2514B | 20 | GF | BD | | 15-0 | 21-51-25 | D03028 | | 1 | | D41102P | 12 | | | 115-199 | |
| 2514R | 20 | GF | BD | | 0-0 | 21-51-25 | D03028 | | 2 | | D41102P | 13 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2500

Page 4

May 17/2006



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|------------------------|------------------------|-------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W2506 | 286N2506 | RIGHT AIR CONDITIONING BAY (continued) | | | |
| 2532Z | | BY | 0-0 21-51-23 | GD00228 | ST.. E *1 |
| 2540B | 20 | GF CS | 15-2 21-52-11 | D40068P | 5 |
| 2540R | 20 | GF CS | 0-0 21-52-11 | D40068P | 10 |
| 2540Z | | CS | 0-0 21-52-11 | D40068P | S/R |
| 3501B | 20 | GG AC | 20-1 21-51-22 | D03000 | 10 |
| 3501B | 20 | GG AC | 21-2 21-51-22 | D03000 | 10 |
| 3501R | 20 | GG AC | 0-0 21-51-22 | D03000 | 11 |
| 3501Y | 20 | GG AC | 0-0 21-51-22 | D03000 | 12 |
| 3501Z | | AC | 0-0 21-51-22 | GD00691 | ST.. E *1 |
| 3502B | 20 | GG AD | 20-1 21-51-22 | D03000 | 5 |
| 3502B | 20 | GG AD | 21-2 21-51-22 | D03000 | 5 |
| 3502R | 20 | GG AD | 0-0 21-51-22 | D03000 | 4 |
| 3502Y | 20 | GG AD | 0-0 21-51-22 | D03000 | 6 |
| 3502Z | | AD | 0-0 21-51-22 | GD00691 | ST.. E *2 |
| 3503B | 20 | GG AE | 8-4 21-51-22 | D03002 | 10 |
| 3503B | 20 | GG AE | 9-5 21-51-22 | D03002 | 10 |
| 3503R | 20 | GG AE | 0-0 21-51-22 | D03002 | 11 |
| 3503Y | 20 | GG AE | 0-0 21-51-22 | D03002 | 12 |
| 3503Z | | AE | 0-0 21-51-22 | GD02034 | ST.. E *1 |
| 3504B | 20 | GG AF | 8-4 21-51-22 | D03002 | 5 |
| 3504B | 20 | GG AF | 9-5 21-51-22 | D03002 | 5 |
| 3504R | 20 | GG AF | 0-0 21-51-22 | D03002 | 4 |
| 3504Y | 20 | GG AF | 0-0 21-51-22 | D03002 | 6 |
| 3504Z | | AF | 0-0 21-51-22 | GD02034 | ST.. E *2 |
| 3505B | 20 | GG AG | 14-2 21-51-22 | D03014 | 5 |
| 3505B | 20 | GG AG | 15-3 21-51-22 | D03014 | 5 |
| 3505R | 20 | GG AG | 0-0 21-51-22 | D03014 | 4 |
| 3505Y | 20 | GG AG | 0-0 21-51-22 | D03014 | 12 |
| 3505Z | | AG | 0-0 21-51-22 | GD00228 | ST.. E |
| 3506B | 20 | GG AH | 13-8 21-51-22 | D03004 | 4 |
| 3506B | 20 | GG AH | 14-9 21-51-22 | D03004 | 4 |
| 3506R | 20 | GG AH | 0-0 21-51-22 | D03004 | 2 |
| 3506Y | 20 | GG AH | 0-0 21-51-22 | D03004 | 6 |
| 3506Z | | AH | 0-0 21-51-22 | GD00257 | ST.. E *2 |
| 3507B | 20 | GG AI | 13-9 21-51-22 | D40068P | 7 |
| 3507B | 20 | GG AI | 14-10 21-51-22 | D40068P | 7 |
| 3507R | 20 | GG AI | 0-0 21-51-22 | D40068P | 6 |
| 3507Y | 20 | GG AI | 0-0 21-51-22 | D40068P | 8 |
| 3507Z | | AI | 0-0 21-51-22 | D40068P | S/R |
| | | | | GD00822 | ST.. E |

WIRE LIST

D280N032

91-21-11

Section W2500

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2506 | 286N2506 | | | RIGHT AIR CONDITIONING BAY (continued) | | | | | | | | | | | |
| 3508B | 20 | GG | BH | | 8-5 | 21-52-21 | D03002 | 8 | | | D40070P | 36 | | | ALL |
| 3508R | 20 | GG | BH | | 0-0 | 21-52-21 | D03002 | 7 | | | D40070P | 35 | | | ALL |
| 3508Y | 20 | GG | BH | | 0-0 | 21-52-21 | D03002 | 9 | | | D40070P | 37 | | | ALL |
| 3508Z | | | BH | | 0-0 | 21-52-21 | GD02034 | ST.. | E | *2 | D40070P | S/R | | | ALL |
| 3510B | 20 | GG | BF | | 13-9 | 21-52-21 | D03004 | 3 | | | D40070P | 12 | | | ALL |
| 3510R | 20 | GG | BF | | 0-0 | 21-52-21 | D03004 | 1 | | | D40070P | 11 | | | ALL |
| 3510Y | 20 | GG | BF | | 0-0 | 21-52-21 | D03004 | 5 | | | D40070P | 13 | | | ALL |
| 3510Z | | | BF | | 0-0 | 21-52-21 | GD00257 | ST.. | E | *2 | D40070P | S/R | | | ALL |
| 4255B | 20 | GH | BG | | 9-4 | 21-52-31 | D04644 | 3 | | | D40070P | 16 | | | ALL |
| 4255G | 20 | GH | BG | | 0-0 | 21-52-31 | D04644 | 5 | | | D40070P | 14 | | | ALL |
| 4255R | 20 | GH | BG | | 0-0 | 21-52-31 | D04644 | 4 | | | D40070P | 15 | | | ALL |
| 4255Y | 20 | GH | BG | | 0-0 | 21-52-31 | D04644 | 6 | | | D40070P | 17 | | | ALL |
| 4255Z | | | BG | | 0-0 | 21-52-31 | GD03150 | ST.. | E | | D40070P | S/R | | | ALL |
| A-BK | | | | | 0-6 | 33-31-21 | SP00318 | | 9 | | L00346 | BLK | | | ALL |
| A-GD | | | | | 0-0 | 30-71-11 | B10064 | =2 | | | GD00687 | AC.. | E | | ALL |
| A-PR | | | | | 0-0 | 30-71-11 | SP00326 | | 9 | | B10063 | =1 | | | ALL |
| A-WT | | | | | 0-0 | 33-31-21 | L00346 | WHT | | | SP01574 | | 9 | | ALL |
| B-BK | | | | | 0-7 | 33-31-21 | S00362 | 3 | C | | L00347 | BLK | | | ALL |
| B-PR | | | | | 0-0 | 30-71-11 | B10063 | =2 | | | SP01580 | | 9 | | ALL |
| B-WT | | | | | 0-0 | 33-31-21 | L00347 | WHT | | | GD00689 | DC.. | E | | ALL |
| C-AC | | | | | 0-0 | 30-71-11 | B00041 | =2 | | | GD00687 | AC.. | E | | ALL |
| C-PN | | | | | 0-0 | 30-71-11 | B00041 | =1 | | | SP00326 | | 9 | | ALL |
| C-PR | | | | | 0-0 | 30-71-11 | B10064 | =1 | | | SP01580 | | 9 | | ALL |
| C-ST | | | | | 0-0 | 30-71-11 | B00041 | =3 | | | GD02448 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2500

Page 7 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2510 | | 286N2510 | | | | RIGHT WHEEL WELL-LIGHTING AND FLIGHT CONTROLS | | | | | | | | | |
| 0005 | 18 | GA | | | 1-6 | 29-35-11 | D00532 | 2 | 18 | | GD00960 | DC.. | E | | 001-099 |
| 0005 | 18 | GA | | | 2-0 | 29-35-11 | D00532 | 2 | 18 | | GD00960 | DC.. | E | | 115-199 |
| 0011 | 16 | GA | | | 1-5 | 28-22-11 | D01838 | 4 | | | GD02673 | ST.. | E | | 001-099 |
| 0011 | 16 | GA | | | 2-0 | 28-22-11 | D01838 | 4 | | | GD02673 | ST.. | E | | 115-199 |
| 0014 | 18 | GA | | | 1-3 | 28-42-11 | D01828 | 4 | 18 | | GD00944 | ST.. | E | | 001-099 |
| 0014 | 18 | GA | | | 2-0 | 28-42-11 | D01828 | 4 | 18 | | GD00944 | ST.. | E | | 115-199 |
| 0048 | 18 | GA | | | 1-4 | 28-42-11 | D01828 | 2 | 18 | | GD00943 | DC.. | E | | 001-099 |
| 0048 | 18 | GA | | | 2-0 | 28-42-11 | D01828 | 2 | 18 | | GD00943 | DC.. | E | | 115-199 |
| 0049 | 18 | GA | | | 2-0 | 27-23-11 | D02886 | 1 | | | GD00940 | DC.. | E | | ALL |
| 0050 | 18 | GA | | | 2-0 | 27-23-11 | D02886 | 9 | | | GD00940 | DC.. | E | | ALL |
| 0058 | 18 | GA | | | 1-7 | 29-21-32 | D05118 | 1 | | | GD02571 | DC.. | E | | 001-099 |
| 0058 | 18 | GA | | | 2-0 | 29-21-32 | D05118 | 1 | | | GD02571 | DC.. | E | | 115-199 |
| 0059 | 18 | GA | | | 1-4 | 29-21-32 | D05120 | 1 | | | GD02573 | DC.. | E | | 001-099 |
| 0059 | 18 | GA | | | 2-0 | 29-21-32 | D05120 | 1 | | | GD02573 | DC.. | E | | 115-199 |
| 0060 | 18 | GA | | | 1-4 | 29-21-32 | D05120 | 9 | | | GD02573 | DC.. | E | | 001-099 |
| 0060 | 18 | GA | | | 2-0 | 29-21-32 | D05120 | 9 | | | GD02573 | DC.. | E | | 115-199 |
| 0061 | 18 | GA | | | 1-7 | 29-21-32 | D05118 | 9 | | | GD02571 | DC.. | E | | 001-099 |
| 0061 | 18 | GA | | | 2-0 | 29-21-32 | D05118 | 9 | | | GD02571 | DC.. | E | | 115-199 |
| 1001 | 18 | GE | AK | | 7-4 | 28-42-11 | D01828 | 3 | 18 | | D40358P | | 7 | | 001-099 |
| 1001 | 18 | GE | AK | | 7-0 | 28-42-11 | D01828 | 3 | 18 | | D40358P | | 7 | | 115-199 |
| 1001Z | | | AK | | 0-0 | 28-42-11 | GD00944 | ST.. | E | | D40358P | S/R | | | ALL |
| 1003 | 20 | GE | AN | | 22-8 | 27-62-11 | D03208 | 4 | | | D40360P | | 18 | | 001-099 |
| 1003 | 20 | GE | AN | | 23-0 | 27-62-11 | D03208 | 4 | | | D40360P | | 18 | | 115-199 |
| 1003Z | | | AN | | 0-0 | 27-62-11 | D03208 | | | AA | D40360P | S/R | | | ALL |
| 1004 | 20 | GE | AO | | 6-9 | 27-62-11 | D03208 | 5 | | | GD00431 | DC.. | E | *1 | 001-099 |
| 1004 | 20 | GE | AO | | 7-0 | 27-62-11 | D03208 | 5 | | | GD00431 | DC.. | E | *1 | 115-199 |
| 1004Z | | | AO | | 0-0 | 27-62-11 | D03208 | | | AA | GD00431 | DC.. | E | *1 | ALL |
| 1005 | 18 | GE | AP | | 6-9 | 27-62-11 | D03208 | 2 | | | GD00431 | DC.. | E | *2 | 001-099 |
| 1005 | 18 | GE | AP | | 7-0 | 27-62-11 | D03208 | 2 | | | GD00431 | DC.. | E | *2 | 115-199 |
| 1005Z | | | AP | | 0-0 | 27-62-11 | D03208 | | | AA | GD00431 | DC.. | E | *2 | ALL |
| 2501B | 20 | 2Z | AA | | 24-3 | 32-61-13 | D40358P | 10 | | | SP01962 | | 9 | | 001-099 |
| 2501B | 20 | 2Z | AA | | 25-0 | 32-61-13 | D40358P | 10 | | | SP01962 | | 9 | | 115-199 |
| 2501R | 20 | 2Z | AA | | 0-0 | 32-61-13 | D40358P | 11 | | | SP01960 | | 9 | | ALL |
| 2501ZI | | | AA | | 0-0 | 32-61-13 | D40358P | DED | | | SP01962 | | 9 | | ALL |
| 2501ZO | | | AA | | 0-0 | 32-61-13 | D40358P | S/R | | | GD00003 | ST.. | E | | ALL |
| 2502B | 20 | 2Z | AB | | 14-8 | 32-61-13 | D40358P | 4 | | | SP01966 | | 9 | | 001-099 |
| 2502B | 20 | 2Z | AB | | 15-0 | 32-61-13 | D40358P | 4 | | | SP01966 | | 9 | | 115-199 |
| 2502R | 20 | 2Z | AB | | 0-0 | 32-61-13 | D40358P | 9 | | | SP01964 | | 9 | | ALL |
| 2502ZI | | | AB | | 0-0 | 32-61-13 | D40358P | DED | | | SP01966 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2510

Page 1

May 17/2006



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|-------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2510 | 286N2510 | | | RIGHT WHEEL WELL-LIGHTING AND FLIGHT CONTROLS (continued) | | | | | | | | | | | |
| A-BA | | | | | 0-6 | 32-61-13 | S10072 | RED | | | SP01964 | | 9 | | ALL |
| A-BB | | | | | 0-6 | 32-61-13 | S10072 | BLU | | | SP01966 | | 9 | | ALL |
| W2512 | 286N2512 | | | RIGHT WHEEL WELL- BRAKES AND HYDRAULICS | | | | | | | | | | | |
| 0001 | 18 | | GA | | 2-0 | 32-12-12 | D02452 | | | AA | GD01250 | ST.. | E | | 001-099 |
| 0001 | 18 | | GA | | 3-0 | 32-12-12 | D02452 | | | AA | GD01250 | ST.. | E | | 115-199 |
| 0017 | 18 | | GA | | 2-0 | 32-12-12 | D02452 | | 2 | | GD02531 | DC.. | E | | 001-099 |
| 0017 | 18 | | GA | | 3-0 | 32-12-12 | D02452 | | 2 | | GD02531 | DC.. | E | | 115-199 |
| 0018 | 18 | | GA | | 3-0 | 32-42-11 | D01696 | | 2 | | GD00952 | DC.. | E | | ALL |
| 0023 | 18 | | GA | | 3-0 | 32-42-11 | D01698 | | 2 | | GD00952 | DC.. | E | | ALL |
| 0024 | 18 | | GA | | 2-0 | 32-12-12 | D02452 | | 3 | | GD01250 | ST.. | E | | 001-099 |
| 0024 | 18 | | GA | | 3-0 | 32-12-12 | D02452 | | 3 | | GD01250 | ST.. | E | | 115-199 |
| 0025 | 18 | | GA | | 2-0 | 29-11-22 | D03066 | | 2 | | GD01581 | DC.. | E | | ALL |
| 0035 | 18 | | GA | | 3-0 | 32-42-11 | V00033 | = GND | E | | GD01176 | ST.. | E | *1 | 001-099 |
| 0035 | 18 | | GA | | 4-0 | 32-42-11 | V00033 | = GND | E | | GD01176 | ST.. | E | *1 | 115-199 |
| 0036 | 18 | | GA | | 3-0 | 32-42-11 | V00035 | = GND | E | | GD01176 | ST.. | E | *1 | 001-099 |
| 0036 | 18 | | GA | | 4-0 | 32-42-11 | V00035 | = GND | E | | GD01176 | ST.. | E | *1 | 115-199 |
| 0037 | 18 | | GA | | 3-0 | 32-42-11 | V00039 | = GND | E | | GD01141 | ST.. | E | *1 | ALL |
| 0038 | 18 | | GA | | 3-0 | 32-42-11 | V00034 | = GND | E | | GD01176 | ST.. | E | *2 | 001-099 |
| 0038 | 18 | | GA | | 4-0 | 32-42-11 | V00034 | = GND | E | | GD01176 | ST.. | E | *2 | 115-199 |
| 0039 | 18 | | GA | | 3-0 | 32-42-11 | V00036 | = GND | E | | GD01176 | ST.. | E | *2 | 001-099 |
| 0039 | 18 | | GA | | 4-0 | 32-42-11 | V00036 | = GND | E | | GD01176 | ST.. | E | *2 | 115-199 |
| 0040 | 18 | | GA | | 3-0 | 32-42-11 | V00040 | = GND | E | | GD01141 | ST.. | E | *1 | ALL |
| 0050 | 18 | | GA | | 2-0 | 32-42-11 | D01688 | | 3 | | GD01171 | ST.. | E | *1 | 001-099 |
| 0050 | 18 | | GA | | 3-0 | 32-42-11 | D01688 | | 3 | | GD01171 | ST.. | E | *1 | 115-199 |
| 0051 | 18 | | GA | | 2-0 | 32-42-11 | D01692 | | 3 | | GD01171 | ST.. | E | *1 | 001-099 |
| 0051 | 18 | | GA | | 3-0 | 32-42-11 | D01692 | | 3 | | GD01171 | ST.. | E | *1 | 115-199 |
| 0052 | 18 | | GA | | 3-0 | 32-42-11 | D01696 | | 3 | | GD01158 | ST.. | E | *1 | ALL |
| 0053 | 18 | | GA | | 2-0 | 32-42-11 | D01690 | | 3 | | GD01171 | ST.. | E | *2 | 001-099 |
| 0053 | 18 | | GA | | 3-0 | 32-42-11 | D01690 | | 3 | | GD01171 | ST.. | E | *2 | 115-199 |
| 0054 | 18 | | GA | | 2-0 | 32-42-11 | D01694 | | 3 | | GD01171 | ST.. | E | *2 | 001-099 |
| 0054 | 18 | | GA | | 3-0 | 32-42-11 | D01694 | | 3 | | GD01171 | ST.. | E | *2 | 115-199 |
| 0055 | 18 | | GA | | 2-0 | 32-42-11 | D01698 | | 3 | | GD01158 | ST.. | E | *2 | 001-099 |
| 0055 | 18 | | GA | | 3-0 | 32-42-11 | D01698 | | 3 | | GD01158 | ST.. | E | *2 | 115-199 |
| 1001 | 18 | | GE | BX | 10-0 | 32-42-11 | D43010P | | 1 | | D01696 | | 1 | | 001-099 |
| 1001 | 18 | | GE | BX | 9-0 | 32-42-11 | D43010P | | 1 | | D01696 | | 1 | | 115-199 |
| 1001Z | | | | BX | 0-0 | 32-42-11 | D43010P | | S/R | | GD01158 | ST.. | E | *1 | ALL |
| 1003 | 18 | | GE | BZ | 26-0 | 32-42-11 | D41818P | | 6 | | D01694 | | 1 | | ALL |
| 1003Z | | | | BZ | 0-0 | 32-42-11 | D41818P | | S/R | | GD01171 | ST.. | E | *3 | ALL |

WIRE LIST

D280N032

91-21-11

Section W2510

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2512 | 286N2512 | | | RIGHT WHEEL WELL- BRAKES AND HYDRAULICS (continued) | | | | | | | | | | | |
| 1005 | 18 | GE | DB | | 26-0 | 32-42-11 | D41818P | 5 | | | D01692 | 1 | | | ALL |
| 1005Z | | | DB | | 0-0 | 32-42-11 | D41818P | S/R | | | GD01171 | ST.. | E | *3 | ALL |
| 1007 | 18 | GE | DD | | 26-0 | 32-42-11 | D41818P | 4 | | | D01690 | 1 | | | ALL |
| 1007Z | | | DD | | 0-0 | 32-42-11 | D41818P | S/R | | | GD01171 | ST.. | E | *3 | ALL |
| 1009 | 18 | GE | DF | | 26-0 | 32-42-11 | D41818P | 1 | | | D01688 | 1 | | | ALL |
| 1009Z | | | DF | | 0-0 | 32-42-11 | D41818P | S/R | | | GD01171 | ST.. | E | *3 | ALL |
| 1011 | 18 | GE | BN | | 10-0 | 32-42-11 | D43010P | 3 | | | D01698 | 1 | | | 001-099 |
| 1011 | 18 | GE | BN | | 9-0 | 32-42-11 | D43010P | 3 | | | D01698 | 1 | | | 115-199 |
| 1011Z | | | BN | | 0-0 | 32-42-11 | D43010P | S/R | | | GD01158 | ST.. | E | *2 | ALL |
| 1013 | 18 | GE | BF | | 24-0 | 32-12-12 | D40362P | 15 | | | S10192 | 3 | C | | ALL |
| 1013Z | | | BF | | 0-0 | 32-12-12 | D40362P | S/R | | | GD02671 | ST.. | E | *4 | 001-099 |
| 1013Z | | | BF | | 0-0 | 32-12-12 | D40362P | S/R | | | GD02671 | ST.. | E | * | 115-199 |
| 1014 | 18 | GE | BE | | 24-0 | 32-12-12 | D40362P | 19 | | | S10192 | 1 | C | | ALL |
| 1014Z | | | BE | | 0-0 | 32-12-12 | D40362P | S/R | | | GD02047 | ST.. | E | | ALL |
| 1015 | 18 | GE | BD | | 33-0 | 32-12-12 | S10192 | 2 | C | | SP00338 | 9 | | | ALL |
| 1015Z | | | BD | | 0-0 | 32-12-12 | GD02671 | ST.. | E | *4 | GD02670 | ST.. | E | *1 | 001-099 |
| 1015Z | | | BD | | 0-0 | 32-12-12 | GD02671 | ST.. | E | * | GD02670 | ST.. | E | * | 115-199 |
| 1016 | 18 | GE | BG | | 20-0 | 32-12-12 | D02452 | 1 | | | SP00338 | 9 | | | ALL |
| 1016Z | | | BG | | 0-0 | 32-12-12 | D02452 | | | AA | GD02670 | ST.. | E | *1 | 001-099 |
| 1016Z | | | BG | | 0-0 | 32-12-12 | D02452 | | | AA | GD02670 | ST.. | E | * | 115-199 |
| 1019 | 18 | GE | AB | | 3-0 | 32-42-11 | D01694 | 2 | | | GD00947 | DC.. | E | *1 | ALL |
| 1019Z | | | AB | | 0-0 | 32-42-11 | GD01171 | ST.. | E | *4 | GD00947 | DC.. | E | *1 | ALL |
| 1020 | 18 | GE | AC | | 3-0 | 32-42-11 | D01692 | 2 | | | GD00947 | DC.. | E | *2 | ALL |
| 1020Z | | | AC | | 0-0 | 32-42-11 | GD01171 | ST.. | E | *4 | GD00947 | DC.. | E | *2 | ALL |
| 1021 | 18 | GE | AD | | 3-0 | 32-42-11 | D01690 | 2 | | | GD00947 | DC.. | E | *3 | ALL |
| 1021Z | | | AD | | 0-0 | 32-42-11 | GD01171 | ST.. | E | *4 | GD00947 | DC.. | E | *3 | ALL |
| 1022 | 18 | GE | AE | | 3-0 | 32-42-11 | D01688 | 2 | | | GD00947 | DC.. | E | *4 | ALL |
| 1022Z | | | AE | | 0-0 | 32-42-11 | GD01171 | ST.. | E | *4 | GD00947 | DC.. | E | *4 | ALL |
| 1041 | 18 | GE | BA | | 27-0 | 29-11-22 | D03066 | 3 | | | D40362P | 18 | 18 | | ALL |
| 1041Z | | | BA | | 0-0 | 29-11-22 | GD02187 | ST.. | E | | D40362P | S/R | | | ALL |
| 2501B | 20 | 2Z | CB | | 31-0 | 32-61-13 | D40362P | 21 | | | SP01994 | | 9 | | ALL |
| 2501R | 20 | 2Z | CB | | 0-0 | 32-61-13 | D40362P | 17 | | | SP01992 | | 9 | | ALL |
| 2501ZI | | | CB | | 0-0 | 32-61-13 | D40362P | DED | | | SP01994 | | 9 | | ALL |
| 2501ZO | | | CB | | 0-0 | 32-61-13 | D40362P | S/R | | | GD00061 | ST.. | E | | ALL |
| 2502B | 20 | 2Z | CC | | 21-0 | 32-61-13 | D40362P | 28 | | | SP01998 | | 9 | | 001-099 |
| 2502B | 20 | 2Z | CC | | 22-0 | 32-61-13 | D40362P | 28 | | | SP01998 | | 9 | | 115-199 |
| 2502R | 20 | 2Z | CC | | 0-0 | 32-61-13 | D40362P | 25 | | | SP01996 | | 9 | | ALL |
| 2502ZI | | | CC | | 0-0 | 32-61-13 | D40362P | DED | | | SP01998 | | 9 | | ALL |
| 2502ZO | | | CC | | 0-0 | 32-61-13 | D40362P | S/R | | | GD01655 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2510

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|---|-------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2512 | 286N2512 | RIGHT WHEEL WELL- BRAKES AND HYDRAULICS (continued) | | | | | | | | | | | | | |
| 2503B | 20 | GF | FA | 23-0 | 23-41-12 | D40362P | 13 | | SP01566 | | 9 | | 001-099 | | |
| 2503R | 20 | GF | FA | 0-0 | 23-41-12 | D40362P | 12 | | SP01564 | | 9 | | 001-099 | | |
| 2503Z | | | FA | 0-0 | 23-41-12 | D40362P | 16 | 18 | SP01568 | | 9 | | 001-099 | | |
| 2521B | 18 | GF | CA | 21-0 | 32-42-12 | D41818P | 3 | | D02666 | 3 | | | 001-099 | | |
| 2521B | 18 | GF | CA | 19-0 | 32-42-12 | D41818P | 3 | | D02666 | 3 | | | 115-199 | | |
| 2521R | 18 | GF | CA | 0-0 | 32-42-12 | D41818P | 2 | | D02666 | 2 | | | ALL | | |
| 2521Z | | | CA | 0-0 | 32-42-12 | D41818P | S/R | | GD01179 | ST.. | E | | ALL | | |
| 3501B | 20 | GG | FB | 14-0 | 29-31-11 | D02488 | 2 | | D40362P | 10 | | | ALL | | |
| 3501R | 20 | GG | FB | 0-0 | 29-31-11 | D02488 | 3 | | D40362P | 11 | | | ALL | | |
| 3501Y | 20 | GG | FB | 0-0 | 29-31-11 | D02488 | 1 | | D40362P | 9 | | | ALL | | |
| 3501Z | | | FB | 0-0 | 29-31-11 | GD01173 | ST.. | E | D40362P | S/R | | | ALL | | |
| 3502B | 20 | GG | FA | 24-0 | 23-41-12 | D40362P | 13 | | SP01566 | | 9 | | 115-199 | | |
| 3502R | 20 | GG | FA | 0-0 | 23-41-12 | D40362P | 12 | | SP01564 | | 9 | | 115-199 | | |
| 3502Y | 20 | GG | FA | 0-0 | 23-41-12 | D40362P | 14 | | SP01568 | | 9 | | 115-199 | | |
| 3502Z | | | FA | 0-0 | 23-41-12 | D40362P | 16 | 18 | SP01568 | DED | | | 115-199 | | |
| A-AA | | | | 0-0 | 23-41-12 | D00427 | RED | | SP01564 | | 9 | | ALL | | |
| A-AB | | | | 0-0 | 23-41-12 | D00427 | BLU | | SP01566 | | 9 | | ALL | | |
| A-AC | | | | 0-0 | 23-41-12 | D00427 | BLK | | SP01568 | | 9 | | ALL | | |
| A-BA | | | | 0-6 | 32-61-13 | S10239 | RED | | SP01992 | | 9 | | ALL | | |
| A-BB | | | | 0-6 | 32-61-13 | S10239 | BLU | | SP01994 | | 9 | | ALL | | |
| A-CA | | | | 0-6 | 32-61-13 | S10241 | RED | | SP01996 | | 9 | | ALL | | |
| A-CB | | | | 0-6 | 32-61-13 | S10241 | BLU | | SP01998 | | 9 | | ALL | | |
| W2514 | 286N2514 | RIGHT WHEEL WELL - FIRE EXTINGUISHING #1, BRAKES & MISC. | | | | | | | | | | | | | |
| 0003 | 18 | GA | | 3-10 | 29-22-11 | D03142 | 1 | | GD00954 | DC.. | E | | 001-099 | | |
| 0003 | 18 | GA | | 3-0 | 29-22-11 | D03142 | 1 | | GD00738 | DC.. | E | | 115-199 | | |
| 0026 | 22 | GA | | 9-8 | 31-31-63 | GD00738 | DC.. | E | D02760 | 6 | | | 001-099 | | |
| 1002 | 18 | HE | AB | 15-3 | 26-17-11 | D02822 | =1 | | SP00300 | | 9 | | 001-099 | | |
| 1002 | 18 | HE | AB | 17-0 | 26-17-11 | D02822 | =1 | | SP00300 | | 9 | | 115-199 | | |
| 1002Z | | | AB | 0-0 | 26-17-11 | GD02323 | ST.. | E | GD02670 | ST.. | E | | ALL | | |
| 1003 | 18 | HE | AC | 11-0 | 26-17-11 | D40364P | 1 | | D02820 | =1 | | | 001-099 | | |
| 1003 | 18 | HE | AC | 13-0 | 26-17-11 | D40364P | 1 | | D02820 | =1 | | | 115-199 | | |
| 1003Z | | | AC | 0-0 | 26-17-11 | D40364P | S/R | | GD02323 | ST.. | E | | ALL | | |
| 1004 | 18 | HE | AD | 12-2 | 26-18-11 | D40364P | 2 | | D01962 | =1 | | | 001-099 | | |
| 1004 | 18 | HE | AD | 13-0 | 26-18-11 | D40364P | 2 | | D01962 | =1 | | | 115-199 | | |
| 1004Z | | | AD | 0-0 | 26-18-11 | D40364P | S/R | | GD02270 | ST.. | E | | ALL | | |
| 1005 | 18 | HE | AE | 9-7 | 26-18-11 | D40364P | 3 | | D01964 | =1 | | | 001-099 | | |
| 1005 | 18 | HE | AE | 10-0 | 26-18-11 | D40364P | 3 | | D01964 | =1 | | | 115-199 | | |
| 1005Z | | | AE | 0-0 | 26-18-11 | D40364P | S/R | | GD02286 | ST.. | E | | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W2510

Page 5

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2510
Page 6
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|---|----|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2516 286N2516 RIGHT WHEEL WELL- FIRE EXTINGUISHING LOOP B, HYDRAULICS & MISC. (continued) | | | | | | | | | | | | | | | | |
| 0032 | 18 | GA | | | | 2-8 | 29-33-11 | D02490 | 2 | | | GD03068 | ST.. | E | | 001-099 |
| 0032 | 18 | GA | | | | 2-3 | 29-33-11 | D02490 | 2 | | | GD03068 | ST.. | E | | 115-199 |
| 0035 | 18 | GA | | | | 3-4 | 29-33-11 | D02492 | 3 | | | GD02086 | ST.. | E | *1 | ALL |
| 0043 | 18 | GA | | | | 6-0 | 28-21-23 | D02446 | 3 | 18 | | GD01179 | ST.. | E | | 001-008 |
| 0043 | 18 | GA | | | | 2-0 | 28-21-23 | D02446 | 3 | 18 | | GD01179 | ST.. | E | | 009-099 |
| 0043 | 18 | GA | | | | 1-6 | 28-21-23 | D02446 | 3 | 18 | | GD01179 | ST.. | E | | 115-199 |
| 0052 | 16 | GA | | | | 2-0 | 33-31-11 | L00072 | = G | E | | GD00942 | AC.. | E | | ALL |
| 0053 | 16 | GA | | | | 2-4 | 33-31-11 | D02256 | 1 | | | GD00447 | AC.. | E | | ALL |
| 0064 | 18 | HL | | | | 1-4 | 29-21-31 | D03248 | 4 | | | GD02277 | ST.. | E | | ALL |
| 0065 | 18 | GA | | | | 1-4 | 29-21-31 | D03248 | 6 | | | GD02276 | DC.. | E | | ALL |
| 0068 | 18 | GA | | | | 1-9 | 29-21-31 | D03252 | 9 | | | GD02278 | DC.. | E | | ALL |
| 0069 | 18 | GA | | | | 1-4 | 29-21-31 | D03248 | 3 | | | GD02276 | DC.. | E | | ALL |
| 0070 | 18 | GA | | | | 1-9 | 29-21-31 | D03252 | 1 | | | GD02278 | DC.. | E | | ALL |
| 0071 | 20 | GA | | | | 0-3 | 29-33-11 | D02490 | 1 | | | D02490 | | | AU | ALL |
| 0072 | 20 | GA | | | | 0-3 | 29-33-11 | D02490 | 6 | | | D02490 | | | AU | ALL |
| 0077 | 18 | HL | | | | 1-4 | 29-21-31 | D04084 | 4 | | | GD02279 | ST.. | E | | ALL |
| 0080 | 16 | HL | | | | 0-6 | 29-21-31 | D04088 | 1 | | | SM00010 | | 9 | | ALL |
| 0082 | 18 | HL | | | | 1-10 | 29-21-31 | D04088 | 3 | | | GD02283 | ST.. | E | | ALL |
| 0083 | 18 | HL | | | | 1-8 | 29-21-31 | D04082 | 2 | | | GD02281 | DC.. | E | | ALL |
| 0085 | 20 | HL | | | | 0-6 | 29-21-31 | D03254 | 6 | | | SM00008 | | 9 | | ALL |
| 0086 | 20 | HL | | | | 0-6 | 29-21-31 | D03254 | 5 | | | SM00008 | | 9 | | ALL |
| 0087 | 18 | HL | | | | 2-4 | 29-21-31 | D03254 | 4 | | | GD02280 | ST.. | E | | ALL |
| 0090 | 18 | GA | | | | 0-6 | 29-21-31 | D40370P | 35 | 18 | | SM00007 | | 9 | | ALL |
| 0091 | 18 | GA | | | | 0-6 | 29-21-31 | D40370P | 36 | 18 | | SM00009 | | 9 | | ALL |
| 0094 | 18 | GA | | | | 3-4 | 29-32-41 | SM00011 | | 9 | | GD03076 | DC.. | E | | 001-099 |
| 0094 | 18 | GA | | | | 0-36 | 29-32-41 | SM00011 | | 9 | | GD03076 | DC.. | E | | 115-199 |
| 0095 | 18 | HL | | | | 0-6 | 29-32-41 | SM00011 | | 9 | | D04696 | | B | | ALL |
| 1-01 | | | | | | 0-0 | 29-21-31 | S10258 | 1 | | | S10258 | CAP | Y | | ALL |
| 1-02 | | | | | | 0-0 | 29-21-31 | S10258 | 2 | | | S10258 | CAP | Y | | ALL |
| 1-03 | | | | | | 0-0 | 29-21-31 | S10258 | 3 | | | S10258 | CAP | Y | | ALL |
| 1-04 | | | | | | 0-14 | 29-21-31 | S10258 | 4 | | | GD02275 | DC.. | E | | ALL |
| 1-05 | | | | | | 0-0 | 29-21-31 | S10258 | 5 | | | SP01514 | | 9 | | ALL |
| 1-06 | | | | | | 0-6 | 29-21-31 | S10258 | 6 | | | SP01514 | CAP | Y | | ALL |
| 1-07 | | | | | | 0-14 | 29-21-31 | S10258 | 7 | | | GD02275 | DC.. | E | | ALL |
| 1-08 | | | | | | 0-6 | 29-21-31 | S10258 | 8 | | | SP01518 | | 9 | | ALL |
| 1-09 | | | | | | 0-6 | 29-21-31 | S10258 | 9 | | | SP01516 | | 9 | | ALL |
| 1-10 | | | | | | 0-6 | 29-21-31 | S10258 | 10 | | | SP01520 | | 9 | | ALL |
| 1-11 | | | | | | 0-6 | 29-21-31 | S10258 | 11 | | | SP01522 | CAP | Y | | ALL |
| 1-12 | | | | | | 0-0 | 29-21-31 | S10258 | 12 | | | SP01522 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2510

Page 7

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2510
Page 8
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | | | | | | | | | |
| W2516 | 286N2516 | | | RIGHT WHEEL WELL- FIRE EXTINGUISHING LOOP B, HYDRAULICS & MISC. (continued) | | | | | | | | | | | |
| 1026 | 20 | GE | DB | | 32-1 | 29-33-11 | D40370P | 15 | | | D02492 | 2 | | | ALL |
| 1026Z | | | DB | | 0-0 | 29-33-11 | D40370P | S/R | | | GD00961 | ST.. | E | *1 | ALL |
| 1027 | 20 | GE | DA | | 3-2 | 29-33-11 | D02492 | 1 | | | D02494 | 3 | | | ALL |
| 1027Z | | | DA | | 0-0 | 29-33-11 | GD00961 | ST.. | E | *1 | GD02086 | ST.. | E | | ALL |
| 1028 | 16 | GE | AL | | 17-8 | 33-31-11 | L00073 | =P | C | | L00072 | =P | C | *5 | ALL |
| 1028Z | | | AL | | 0-0 | 33-31-11 | GD01630 | ST.. | E | | GD01929 | ST.. | E | | ALL |
| 1032 | 18 | GE | BY | | 34-6 | 32-12-12 | S10365 | 2 | C | | SP00053 | 9 | | | ALL |
| 1032Z | | | BY | | 0-0 | 32-12-12 | GD02671 | ST.. | E | *3 | GD01073 | ST.. | E | | ALL |
| 1033 | 18 | GE | AB | | 17-0 | 33-31-11 | S00318 | 3 | C | | D02256 | 3 | | | ALL |
| 1033Z | | | AB | | 0-0 | 33-31-11 | GD02047 | ST.. | E | | GD00446 | ST.. | E | | ALL |
| 1038 | 18 | GE | AT | | 4-10 | 32-12-12 | L00490 | =G | C | | GD02393 | DC.. | E | *1 | ALL |
| 1038Z | | | AT | | 0-0 | 32-12-12 | GD02138 | ST.. | E | | GD02393 | DC.. | E | *1 | ALL |
| 1043 | 16 | GE | AY | | 2-0 | 29-21-31 | D04088 | 2 | | | GD02282 | DC.. | E | *1 | ALL |
| 1043Z | | | AY | | 0-0 | 29-21-31 | GD02283 | ST.. | E | | GD02282 | DC.. | E | *1 | ALL |
| 1050 | 18 | GE | EE | | 34-6 | 32-12-12 | S10365 | 1 | C | | SP01090 | 9 | | | ALL |
| 1050Z | | | EE | | 0-0 | 32-12-12 | GD02671 | ST.. | E | *3 | GD01073 | ST.. | E | | ALL |
| 2501B | 20 | HQ | AA | | 10-11 | 29-21-31 | D03254 | 1 | | | D04080 | 1 | | | ALL |
| 2501R | 20 | HQ | AA | | 0-0 | 29-21-31 | D03254 | 2 | | | D04080 | 2 | | | ALL |
| 2501Z | | | AA | | 0-0 | 29-21-31 | D03254 | 3 | | | GD02296 | ST.. | E | | ALL |
| 2502B | 18 | GF | AE | | 14-10 | 29-32-41 | D40370P | 33 | 18 | | SM00011 | 9 | | | 001-099 |
| 2502B | 18 | GF | AE | | 16-1 | 29-32-41 | D40370P | 33 | 18 | | SM00011 | 9 | | | 115-199 |
| 2502R | 18 | GF | AE | | 0-0 | 29-32-41 | D40370P | 31 | 18 | | D04696 | A | | | ALL |
| 2502Z | | | AE | | 0-0 | 29-32-41 | D40370P | S/R | | | GD03068 | ST.. | E | *1 | 001-099 |
| 2502Z | | | AE | | 0-0 | 29-32-41 | D40370P | S/R | | | GD03068 | ST.. | E | * | 115-199 |
| 2504B | 20 | GF | AI | | 14-0 | 28-21-23 | D02446 | 5 | | | D40370P | 1 | | | 001-099 |
| 2504B | 20 | GF | AI | | 14-4 | 28-21-23 | D02446 | 5 | | | D40370P | 1 | | | 115-199 |
| 2504R | 20 | GF | AI | | 0-0 | 28-21-23 | D02446 | 2 | | | D40370P | 20 | | | 001-009, 115-199 |
| 2504R | 20 | GF | AI | | 0-0 | 28-21-23 | D02446 | 2 | 16 | * | D40370P | 20 | | | 010-099 |
| 2504Z | | | AI | | 0-0 | 28-21-23 | GD01179 | ST.. | E | | D40370P | S/R | | | ALL |
| 2505B | 20 | GF | AO | | 13-9 | 32-44-11 | D02646 | 8 | | | D40370P | 3 | | | 001-099 |
| 2505B | 20 | GF | AO | | 13-9 | 32-44-11 | D02646 | 8 | | | D40370P | 22 | | | 115-199 |
| 2505R | 20 | GF | AO | | 0-0 | 32-44-11 | D02646 | 10 | | | D40370P | 22 | | | 001-099 |
| 2505R | 20 | GF | AO | | 0-0 | 32-44-11 | D02646 | 10 | | | D40370P | 3 | | | 115-199 |
| 2505Z | | | AO | | 0-0 | 32-44-11 | GD00348 | ST.. | E | | D40370P | S/R | | | ALL |
| 2506B | 20 | GF | BJ | | 4-7 | 29-21-31 | D03252 | 2 | | | D04084 | 1 | | | ALL |
| 2506R | 20 | GF | BJ | | 0-0 | 29-21-31 | D03252 | 4 | | | D04084 | 5 | | | ALL |
| 2506Z | | | BJ | | 0-0 | 29-21-31 | GD02295 | ST.. | E | | GD02279 | ST.. | E | | ALL |
| 2520B | 18 | GF | BQ | | 17-2 | 32-12-12 | D40370P | 21 | 18 | | SP01244 | 9 | | | ALL |
| 2520R | 18 | GF | BQ | | 0-0 | 32-12-12 | D40370P | 25 | 18 | | SP01246 | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2510

Page 9

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2510
Page 10
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | | | | To | | | | |
|--------------|-----------------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2516 | 286N2516 | RIGHT WHEEL WELL- FIRE EXTINGUISHING LOOP B, HYDRAULICS & MISC. (continued) | | | | | | | | | |
| T-B | | 0-0 28-21-23 | R10411 | | BLU | | GD00959 | DC.. | GW | | 010-099 |
| T-R | | 0-0 28-21-23 | R10411 | | RED | | D02446 | 2 | 16 | * | 010-099 |
| W-B | | 0-0 SPARE | R10411 | | CAP | Y | R10411 | | BLU | | 010-099 |
| W-R | | 0-0 SPARE | R10411 | | CAP | Y | R10411 | | RED | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W2510

Page 11 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2520 | 286N2520 | | | RIGHT WHEELWELL-ALTERNATE LANDING GEAR EXTENSION | | | | | | | | | | | |
| 0001 | 08 | | HA | | 34-0 | 32-35-11 | D03352 | | A | | SM00002 | | GX | | ALL |
| 0002 | 08 | | HA | | 2-0 | 32-35-11 | D03352 | | B | | GD00937 | DC.. | F | | 001-099 |
| 0002 | 08 | | HA | | 1-10 | 32-35-11 | D03352 | | B | | GD00937 | DC.. | F | | 115-199 |
| 0003 | 08 | | HA | | 2-0 | 32-35-11 | D03352 | | C | | GD00938 | ST.. | F | | 001-099 |
| 0003 | 08 | | HA | | 1-10 | 32-35-11 | D03352 | | C | | GD00938 | ST.. | F | | 115-199 |
| 0004 | 06 | | 43 | | 34-0 | 32-35-11 | SM00001 | | | GX | SM00002 | | GX | | 001-099 |
| 0004 | 06 | | 43 | | 33-0 | 32-35-11 | SM00001 | | | GX | SM00002 | | GX | | 115-199 |
| 0005 | 08 | | HA | | 3-0 | 32-35-11 | SM00001 | | | GX | K10369 | A2 | E | | 001-099 |
| 0005 | 08 | | HA | | 1-11 | 32-35-11 | SM00001 | | | GX | K10369 | A2 | E | | 115-199 |
| YAAA | | | | | 0-0 | 32-35-11 | GD02124 | | ST.. | E | GD00292 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2520

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2602 | | 286N2602 | | | | E/E BAY TO AFT CARGO BAY | | | | | | | | | |
| 0001 | 18 | GA | | | 87-0 | SPARE | D40178J | | | | D40184P | 1 | | | ALL |
| 0002 | 20 | GA | | | 87-0 | 30-71-21 | D40176J | | | 13 | D40184P | 2 | | | ALL |
| 0003 | 20 | GA | | | 87-0 | 30-71-21 | D40176J | | | 11 | D40184P | 3 | | | ALL |
| 0005 | 20 | GA | | | 87-0 | 30-71-11 | D40176J | | | 15 | D40184P | 5 | | | ALL |
| 0006 | 16 | GA | | | 93-0 | 52-35-11 | D40178J | | | 6 | D40188P | 7 | | | ALL |
| 0007 | 16 | GA | | | 93-0 | 52-35-11 | D40178J | | | 7 | D40188P | 10 | | | ALL |
| 0008 | 16 | GA | | | 93-0 | 52-35-11 | D40178J | | | 8 | D40188P | 4 | | | ALL |
| 0010 | 22 | GA | | | 92-0 | 52-35-11 | D40176J | | | 50 | D41930P | 1 | | | 001-099 |
| 0010 | 22 | GA | | | 32-0 | 52-35-11 | D40186P | | | 20 | D41930P | 1 | | | 115-199 |
| 0011 | 22 | GA | | | 92-0 | 52-35-11 | D40176J | | | 51 | D41930P | 2 | | | 001-099 |
| 0011 | 22 | GA | | | 32-0 | 52-35-11 | D40186P | | | 21 | D41930P | 2 | | | 115-199 |
| 0012 | 18 | GA | | | 87-0 | 21-58-21 | D40178J | | | 13 | D40184P | 13 | | | ALL |
| 0013 | 18 | GA | | | 87-0 | 21-58-21 | D40178J | | | 14 | D40184P | 14 | | | ALL |
| 0014 | 18 | GA | | | 87-0 | 21-58-21 | D40178J | | | 15 | D40184P | 15 | | | ALL |
| 0015 | 20 | GA | | | 87-0 | 21-58-21 | D40176J | | | 25 | D40186P | 7 | | | ALL |
| 0016 | 24 | GK | | | 87-0 | SPARE | D40176J | | | 26 | D40186P | 8 | | | ALL |
| 0017 | 20 | GA | | | 80-0 | 21-31-21 | D40176J | | | 27 | D40182P | 27 | | | ALL |
| 0018 | 18 | GA | | | 5-0 | 33-31-21 | D40188P | | | 14 | SP00081 | | 9 | | ALL |
| 0019 | 22 | GA | | | 93-0 | SPARE | D40188P | | | 2 | D40176J | 14 | | | 001-099 |
| 0019 | 22 | GA | | | 93-0 | 25-51-21 | D40188P | | | 5 | D40176J | 14 | | | 115-199 |
| 0020 | 18 | GA | | | 93-0 | SPARE | D40188P | | | 3 | D40178J | 18 | | | 001-099 |
| 0020 | 18 | GA | | | 93-0 | 25-51-21 | D40188P | | | 3 | D40178J | 18 | | | 115-199 |
| 0021 | 18 | GA | | | 93-0 | SPARE | D40188P | | | 6 | D40178J | 4 | | | 001-099 |
| 0021 | 18 | GA | | | 93-0 | 25-51-21 | D40188P | | | 6 | D40178J | 4 | | | 115-199 |
| 0022 | 22 | GA | | | 87-0 | 38-14-11 | D40176J | | | 1 | D40186P | 1 | | | ALL |
| 0023 | 22 | GA | | | 87-0 | 38-14-11 | D40176J | | | 2 | D40186P | 2 | | | ALL |
| 0024 | 22 | GA | | | 87-0 | 38-14-11 | D40176J | | | 3 | D40186P | 3 | | | ALL |
| 0029 | 20 | GA | | | 5-0 | 21-44-11 | D01638 | | | 1 | GD00735 | DC.. | E | | ALL |
| 0030 | 20 | GA | | | 108-0 | 21-44-11 | D01638 | | | 2 | D40186P | 18 | | | ALL |
| 0031 | 24 | GK | | | 108-0 | 21-44-11 | D01642 | | | 6 | D40186P | 17 | | | ALL |
| 0032 | 24 | GK | | | 108-0 | 21-44-11 | D01642 | | | 5 | D40186P | 16 | | | ALL |
| 0033 | 18 | GA | | | 108-0 | 21-44-11 | D01642 | | | 1 | D40184P | 10 | | | ALL |
| 0034 | 18 | GA | | | 108-0 | 21-44-11 | D01642 | | | 2 | D40184P | 11 | | | ALL |
| 0035 | 18 | GA | | | 108-0 | 21-44-11 | D01642 | | | 3 | D40184P | 12 | | | ALL |
| 0036 | 18 | GA | | | 93-0 | SPARE | D40188P | | | 9 | D40178J | 19 | | | 001-099 |
| 0036 | 18 | GA | | | 93-0 | 25-51-21 | D40188P | | | 8 | D40178J | 19 | | | 115-199 |
| 0037 | 18 | GA | | | 93-0 | 33-37-21 | D40188P | | | 1 | D40178J | 16 | | | ALL |
| 0043 | 18 | GA | | | 87-0 | 38-15-11 | D40184P | | | 6 | D40178J | 9 | | | ALL |
| 0044 | 20 | GA | | | 87-0 | SPARE | D40176J | | | 4 | D40186P | 4 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2600

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2602 | 286N2602 | | | | E/E BAY TO AFT CARGO BAY (continued) | | | | | | | | | | | |
| 0044 | 20 | | GA | | 87-0 | 38-14-11 | D40176J | | 4 | | | D40186P | | 4 | | 115-199 |
| 0045 | 20 | | GA | | 87-0 | SPARE | D40176J | | 5 | | | D40186P | | 5 | | 001-099 |
| 0045 | 20 | | GA | | 87-0 | 38-14-11 | D40176J | | 5 | | | D40186P | | 5 | | 115-199 |
| 0046 | 24 | | GK | | 87-0 | SPARE | D40176J | | 32 | | | D40186P | | 9 | | ALL |
| 0048 | 22 | | GA | | 87-0 | SPARE | D40176J | | 34 | | | D40186P | | 11 | | 001-099 |
| 0049 | 22 | | GA | | 87-0 | SPARE | D40176J | | 35 | | | D40186P | | 12 | | 001-099 |
| 0050 | 20 | | GA | | 87-0 | SPARE | D40176J | | 36 | | | D40186P | | 13 | | 001-099 |
| 0051 | 20 | | GA | | 87-0 | SPARE | D40176J | | 37 | | | D40186P | | 14 | | 001-099 |
| 0058 | 16 | | GA | | 4-0 | 21-44-11 | D01642 | | 7 | | | GD00732 | ST.. | E | | ALL |
| 0059 | 20 | | GA | | 93-0 | SPARE | D40188P | | 5 | | | D40176J | | 33 | | 001-099 |
| 0060 | 20 | | GA | | 93-0 | SPARE | D40188P | | 8 | | | D40176J | | 12 | | 001-099 |
| 0063 | 22 | | GA | | 90-0 | 52-35-11 | SP01052 | | | 9 | | D40176J | | 19 | | 001-099 |
| 0063 | 22 | | GA | | 18-0 | 52-35-11 | SP01052 | | | 9 | | D40186P | | 22 | | 115-199 |
| 0064 | 18 | | GA | | 87-0 | 38-15-11 | D40184P | | 7 | | | D40178J | | 10 | | ALL |
| 0065 | 18 | | GA | | 87-0 | 38-15-11 | D40184P | | 8 | | | D40178J | | 11 | | ALL |
| 0066 | 18 | | GA | | 87-0 | 38-15-11 | D40184P | | 9 | | | D40178J | | 12 | | ALL |
| 0080 | 22 | | GA | | 87-0 | SPARE | D40186P | | 27 | | | D40176J | | 44 | | 001-099 |
| 0080 | 22 | | GA | | 87-0 | 21-58-24 | D40186P | | 27 | | | D40176J | | 44 | | 115-199 |
| 0081 | 22 | | GA | | 87-0 | SPARE | D40186P | | 28 | | | D40176J | | 45 | | 001-099 |
| 0081 | 22 | | GA | | 87-0 | 21-58-24 | D40186P | | 28 | | | D40176J | | 45 | | 115-199 |
| 0082 | 24 | | GK | | 87-0 | SPARE | D40186P | | 29 | | | D40176J | | 46 | | 001-099 |
| 0082 | 22 | | GA | | 87-0 | 21-58-24 | D40186P | | 29 | | | D40176J | | 46 | | 115-199 |
| 0083 | 24 | | GK | | 87-0 | SPARE | D40186P | | 31 | | | D40176J | | 47 | | 001-099 |
| 0083 | 24 | | GK | | 87-0 | 21-58-24 | D40186P | | 31 | | | D40176J | | 47 | | 115-199 |
| 0084 | 24 | | GK | | 87-0 | SPARE | D40186P | | 30 | | | D40176J | | 48 | | 001-099 |
| 0084 | 24 | | GK | | 87-0 | 21-58-24 | D40186P | | 30 | | | D40176J | | 48 | | 115-199 |
| 2001B | 24 | | GL | AC | 92-0 | 52-35-11 | D40176J | | 18 | | | D41930P | | 4 | | ALL |
| 2001R | 24 | | GL | AC | 0-0 | 52-35-11 | D40176J | | 17 | | | D41930P | | 3 | | ALL |
| 2002B | 24 | | GL | AB | 92-0 | 52-71-21 | D40176J | | 20 | | | D41930P | | 6 | | 115-199 |
| 2002R | 24 | | GL | AB | 0-0 | 52-71-21 | D40176J | | 19 | | | D41930P | | 5 | | 115-199 |
| 2003B | 24 | | GL | AE | 92-0 | 52-35-11 | D41930P | | 8 | | | D40176J | | 22 | | ALL |
| 2003R | 24 | | GL | AE | 0-0 | 52-35-11 | D40176J | | 21 | | | D41930P | | 7 | | ALL |
| 2005B | 24 | | GL | AG | 92-0 | 52-71-21 | D40176J | | 31 | | | D41930P | | 13 | | ALL |
| 2005R | 24 | | GL | AG | 0-0 | 52-71-21 | D40176J | | 30 | | | D41930P | | 12 | | ALL |
| 2006B | 24 | | GL | AH | 38-0 | 21-61-11 | D40186P | | 24 | | | D02552 | | 2 | | 001-099 |
| 2006B | 24 | | GL | AH | 37-0 | 21-61-11 | D40186P | | 24 | | | D02552 | | 2 | | 115-199 |
| 2006R | 24 | | GL | AH | 0-0 | 21-61-11 | D40186P | | 23 | | | D02552 | | 1 | | ALL |
| 2013B | 24 | | GL | AP | 80-0 | 21-31-21 | D40182P | | 29 | | | D40176J | | 29 | | ALL |
| 2013R | 24 | | GL | AP | 0-0 | 21-31-21 | D40182P | | 28 | | | D40176J | | 28 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2600

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2602 | 286N2602 | | | E/E BAY TO AFT CARGO BAY (continued) | | | | | | | | | | | |
| 2112B | 20 | GB | AR | | 80-0 | 21-31-21 | D40182P | 10 | | | D40176J | 10 | | | ALL |
| 2112R | 20 | GB | AR | | 0-0 | 21-31-21 | D40182P | 9 | | | D40176J | 9 | | | ALL |
| 2501B | 24 | G2 | AA | | 80-0 | 21-31-21 | D40176J | 7 | | | D40182P | 7 | | | ALL |
| 2501R | 24 | G2 | AA | | 0-0 | 21-31-21 | D40176J | 6 | | | D40182P | 6 | | | ALL |
| 2501Z | | | AA | | 0-0 | 21-31-21 | D40176J | 8 | | | D40182P | 8 | | | ALL |
| W2604 | 286N2604 | | | P32 TO HYD BAY - LEFT DEMAND PUMP | | | | | | | | | | | |
| 0001 | 04 | 43 | | | 67-0 | 29-11-12 | M10001 | A2 | H4 | | SM00001 | | GU | | 001-099 |
| 0001 | 04 | 43 | | | 66-0 | 29-11-12 | M10001 | A2 | H4 | | SM00001 | | GU | | 115-199 |
| 0002 | 04 | 43 | | | 67-0 | 29-11-12 | M10001 | B2 | H4 | | SM00002 | | GU | | 001-099 |
| 0002 | 04 | 43 | | | 66-0 | 29-11-12 | M10001 | B2 | H4 | | SM00002 | | GU | | 115-199 |
| 0003 | 04 | 43 | | | 67-0 | 29-11-12 | M10001 | C2 | H4 | | SM00003 | | GU | | 001-099 |
| 0003 | 04 | 43 | | | 66-0 | 29-11-12 | M10001 | C2 | H4 | | SM00003 | | GU | | 115-199 |
| 0004 | 08 | HA | | | 14-0 | 29-11-12 | SM00001 | | | GU | D02150 | A | | | 001-099 |
| 0004 | 08 | HA | | | 15-0 | 29-11-12 | SM00001 | | | GU | D02150 | A | | | 115-199 |
| 0005 | 08 | HA | | | 14-0 | 29-11-12 | SM00002 | | | GU | D02150 | B | | | 001-099 |
| 0005 | 08 | HA | | | 15-0 | 29-11-12 | SM00002 | | | GU | D02150 | B | | | 115-199 |
| 0006 | 08 | HA | | | 15-0 | 29-11-12 | SM00003 | | | GU | D02150 | C | | | 001-099 |
| 0006 | 08 | HA | | | 16-0 | 29-11-12 | SM00003 | | | GU | D02150 | C | | | 115-199 |
| 0007 | 20 | HL | | | 81-0 | 29-11-12 | TB0132X | B009 | BJ | | D03398 | 2 | | | 115-199 |
| 0008 | 18 | HL | | | 2-0 | 29-32-11 | D03398 | 1 | | | GD00669 | DC.. | E | | ALL |
| 0009 | 08 | HA | | | 3-0 | 29-11-12 | D02150 | D | | | GD00454 | ST.. | F | | ALL |
| 0010 | 18 | HL | | | 63-0 | 29-32-11 | SP00011 | | 9 | | D03398 | 3 | | | 001-099 |
| 0010 | 18 | HL | | | 70-0 | 29-32-11 | SP00011 | | 9 | | D03398 | 3 | | | 115-199 |
| YAAB | | | | | 0-0 | 29-11-12 | GD00817 | ST.. | E | | GD00454 | ST.. | F | | ALL |
| YAZA | | | | | 0-0 | 29-32-11 | GD00817 | ST.. | E | | GD00827 | ST.. | E | | 001-099 |
| YAZA | | | | | 0-0 | 29-11-12 | GD00817 | ST.. | E | | GD00827 | ST.. | E | | 115-199 |
| W2605 | 286N2605 | | | E2-1, E3-1 & E5-1 TO AFT BODY DISCONNECT-CHANNEL LEFT | | | | | | | | | | | |
| 0001 | 22 | GA | | | 130-0 | 22-11-12 | D41691P | 1 | | | D40491P | 1 | | | ALL |
| 0002 | 22 | GA | | | 130-0 | 22-11-12 | D41691P | 29 | | | D40491P | 35 | | | ALL |
| 0003 | 22 | GA | | | 130-0 | 22-11-12 | D41691P | 31 | | | D40471J | 24 | | | ALL |
| 0004 | 22 | GA | | | 130-0 | 22-11-12 | D41691P | 17 | | | D40471J | 3 | | | ALL |
| 0006 | 20 | GA | | | 124-0 | 27-31-12 | D41841P | 1 | | | D40491P | 13 | | | 001-099 |
| 0006 | 20 | GA | | | 125-0 | 27-31-12 | D41841P | 1 | | | D40491P | 13 | | | 115-199 |
| 0007 | 20 | GA | | | 124-0 | 27-31-12 | D41841P | 2 | | | D40491P | 14 | | | 001-099 |
| 0007 | 20 | GA | | | 125-0 | 27-31-12 | D41841P | 2 | | | D40491P | 14 | | | 115-199 |
| 0008 | 20 | GA | | | 124-0 | 27-31-12 | D41841P | 3 | | | D40491P | 15 | | | 001-099 |
| 0008 | 20 | GA | | | 125-0 | 27-31-12 | D41841P | 3 | | | D40491P | 15 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2600

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2605 | 286N2605 | | | E2-1, E3-1 & E5-1 TO AFT BODY DISCONNECT-CHANNEL LEFT (continued) | | | | | | | | | | | |
| 0009 | 20 | | GA | | 124-0 | 27-31-12 | D41841P | | 4 | | D40491P | | 16 | | 001-099 |
| 0009 | 20 | | GA | | 125-0 | 27-31-12 | D41841P | | 4 | | D40491P | | 16 | | 115-199 |
| 0016 | 22 | | GA | | 124-0 | 27-48-11 | D41841P | | 13 | | D40697P | | 13 | | 001-099 |
| 0016 | 22 | | GA | | 125-0 | 27-48-11 | D41841P | | 13 | | D40697P | | 13 | | 115-199 |
| 0017 | 22 | | GA | | 124-0 | 27-48-11 | D41841P | | 14 | | D40697P | | 14 | | 001-099 |
| 0017 | 22 | | GA | | 125-0 | 27-48-11 | D41841P | | 14 | | D40697P | | 14 | | 115-199 |
| 0018 | 22 | | GA | | 124-0 | 27-48-11 | D41841P | | 15 | | D40697P | | 15 | | 001-099 |
| 0018 | 22 | | GA | | 125-0 | 27-48-11 | D41841P | | 15 | | D40697P | | 15 | | 115-199 |
| 0019Y | 20 | | QB | | 124-0 | 27-41-11 | D41841P | | 5 | | D40697P | | 1 | | 001-099 |
| 0019Y | 20 | | QB | | 125-0 | 27-41-11 | D41841P | | 5 | | D40697P | | 1 | | 115-199 |
| 0020Y | 20 | | QB | | 124-0 | 27-41-11 | D41841P | | 6 | | D40697P | | 2 | | 001-099 |
| 0020Y | 20 | | QB | | 125-0 | 27-41-11 | D41841P | | 6 | | D40697P | | 2 | | 115-199 |
| 0021Y | 22 | | QB | | 124-0 | 27-41-11 | D41841P | | 7 | | D40697P | | 3 | | 001-099 |
| 0021Y | 22 | | QB | | 125-0 | 27-41-11 | D41841P | | 7 | | D40697P | | 3 | | 115-199 |
| 0022Y | 22 | | QB | | 124-0 | 27-41-11 | D41841P | | 8 | | D40697P | | 4 | | 001-099 |
| 0022Y | 22 | | QB | | 125-0 | 27-41-11 | D41841P | | 8 | | D40697P | | 4 | | 115-199 |
| 0023Y | 22 | | QB | | 124-0 | 27-41-11 | D41841P | | 9 | | D40697P | | 5 | | 001-099 |
| 0023Y | 22 | | QB | | 125-0 | 27-41-11 | D41841P | | 9 | | D40697P | | 5 | | 115-199 |
| 0024Y | 22 | | QB | | 124-0 | SPARE | D41841P | | 10 | | D40697P | | 6 | | 001-099 |
| 0024Y | 22 | | QB | | 125-0 | SPARE | D41841P | | 10 | | D40697P | | 6 | | 115-199 |
| 2001B | 22 | | GB | AA | 130-0 | 22-11-11 | D41691P | | 5 | | D40491P | | 3 | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 22-11-11 | D41691P | | 6 | | D40491P | | 4 | | ALL |
| 2002B | 22 | | GB | AB | 130-0 | 22-11-11 | D41691P | | 7 | | D40471J | | 2 | | ALL |
| 2002R | 22 | | GB | AB | 0-0 | 22-11-11 | D41691P | | 8 | | D40471J | | 1 | | ALL |
| 2003B | 22 | | GB | AC | 130-0 | 22-12-11 | D41691P | | 9 | | D40491P | | 12 | | ALL |
| 2003R | 22 | | GB | AC | 0-0 | 22-12-11 | D41691P | | 10 | | D40491P | | 11 | | ALL |
| 2004B | 22 | | GB | AD | 130-0 | 22-13-11 | D41691P | | 11 | | D40471J | | 6 | | ALL |
| 2004R | 22 | | GB | AD | 0-0 | 22-13-11 | D41691P | | 12 | | D40471J | | 16 | | ALL |
| 2007B | 24 | | GL | AK | 135-0 | 27-48-21 | D41835P | | 5 | | D40697P | | 12 | | 001-099 |
| 2007B | 24 | | GL | AK | 136-0 | 27-48-21 | D41835P | | 5 | | D40697P | | 12 | | 115-199 |
| 2007R | 24 | | GL | AK | 0-0 | 27-48-21 | D41835P | | 4 | | D40697P | | 11 | | ALL |
| 2010B | 22 | | GB | AV | 130-0 | 22-11-11 | D41691P | | 35 | | D40491P | | 2 | | ALL |
| 2010R | 22 | | GB | AV | 0-0 | 22-11-11 | D41691P | | 34 | | D40491P | | 34 | | ALL |
| 3001B | 22 | | GC | AE | 130-0 | 22-12-11 | D41691P | | 13 | | D40491P | | 6 | | ALL |
| 3001R | 22 | | GC | AE | 0-0 | 22-12-11 | D41691P | | 14 | | D40491P | | 5 | | ALL |
| 3001Y | 22 | | GC | AE | 0-0 | 22-12-11 | D41691P | | 15 | | D40491P | | 7 | | ALL |
| 3002B | 22 | | GC | AF | 130-0 | 22-12-11 | D41691P | | 16 | | D40491P | | 9 | | ALL |
| 3002R | 22 | | GC | AF | 0-0 | 22-12-11 | D41691P | | 4 | | D40491P | | 8 | | ALL |
| 3002Y | 22 | | GC | AF | 0-0 | 22-12-11 | D41691P | | 18 | | D40491P | | 10 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2600

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2605 | 286N2605 | | | E2-1, E3-1 & E5-1 TO AFT BODY DISCONNECT-CHANNEL LEFT (continued) | | | | | | | | | | | |
| 3003B | 22 | GC | AG | | 130-0 | 22-13-11 | D41691P | 19 | | | D40471J | 8 | | | ALL |
| 3003R | 22 | GC | AG | | 0-0 | 22-13-11 | D41691P | 20 | | | D40471J | 7 | | | ALL |
| 3003Y | 22 | GC | AG | | 0-0 | 22-13-11 | D41691P | 21 | | | D40471J | 9 | | | ALL |
| 3004B | 22 | GC | AH | | 130-0 | 22-13-11 | D41691P | 22 | | | D40471J | 12 | | | ALL |
| 3004R | 22 | GC | AH | | 0-0 | 22-13-11 | D41691P | 23 | | | D40471J | 11 | | | ALL |
| 3004Y | 22 | GC | AH | | 0-0 | 22-13-11 | D41691P | 24 | | | D40471J | 13 | | | ALL |
| 3005B | 22 | GC | AL | | 130-0 | 22-13-11 | D41691P | 27 | | | D40471J | 18 | | | ALL |
| 3005R | 22 | GC | AL | | 0-0 | 22-13-11 | D41691P | 26 | | | D40471J | 17 | | | ALL |
| 3005Y | 22 | GC | AL | | 0-0 | 22-13-11 | D41691P | 28 | | | D40471J | 19 | | | ALL |
| 3007B | 24 | GM | AJ | | 135-0 | 27-48-21 | D41835P | 2 | | | D40697P | 9 | | | 001-099 |
| 3007B | 24 | GM | AJ | | 136-0 | 27-48-21 | D41835P | 2 | | | D40697P | 9 | | | 115-199 |
| 3007R | 24 | GM | AJ | | 0-0 | 27-48-21 | D41835P | 1 | | | D40697P | 8 | | | ALL |
| 3007Y | 24 | GM | AJ | | 0-0 | 27-48-21 | D41835P | 3 | | | D40697P | 10 | | | ALL |
| 3009B | 22 | GC | AM | | 130-0 | 22-12-11 | D41691P | 37 | | | D40491P | 37 | | | ALL |
| 3009R | 22 | GC | AM | | 0-0 | 22-12-11 | D41691P | 36 | | | D40491P | 36 | | | ALL |
| 3009Y | 22 | GC | AM | | 0-0 | 22-12-11 | D41691P | 38 | | | D40491P | 38 | | | ALL |
| 3010B | 22 | GC | AN | | 130-0 | 22-12-11 | D41691P | 40 | | | D40491P | 18 | | | ALL |
| 3010R | 22 | GC | AN | | 0-0 | 22-12-11 | D41691P | 39 | | | D40491P | 17 | | | ALL |
| 3010Y | 22 | GC | AN | | 0-0 | 22-12-11 | D41691P | 41 | | | D40491P | 19 | | | ALL |
| W2606 | 286N2606 | | | P31 TO HYD BAY - RIGHT DEMAND PUMP | | | | | | | | | | | |
| 0001 | 04 | 43 | | | 69-0 | 29-11-22 | M10005 | A2 | H4 | | SM00001 | | GU | | 001-099 |
| 0001 | 04 | 43 | | | 66-9 | 29-11-22 | M10005 | A2 | H4 | | SM00001 | | GU | | 115-199 |
| 0002 | 04 | 43 | | | 67-0 | 29-11-22 | M10005 | B2 | H4 | | SM00002 | | GU | | 001-099 |
| 0002 | 04 | 43 | | | 66-4 | 29-11-22 | M10005 | B2 | H4 | | SM00002 | | GU | | 115-199 |
| 0003 | 04 | 43 | | | 67-0 | 29-11-22 | M10005 | C2 | H4 | | SM00003 | | GU | | 001-099 |
| 0003 | 04 | 43 | | | 65-11 | 29-11-22 | M10005 | C2 | H4 | | SM00003 | | GU | | 115-199 |
| 0004 | 08 | HA | | | 14-0 | 29-11-22 | SM00001 | | | GU | D02202 | A | | | 001-099 |
| 0004 | 08 | HA | | | 15-2 | 29-11-22 | SM00001 | | | GU | D02202 | A | | | 115-199 |
| 0005 | 08 | HA | | | 15-0 | 29-11-22 | SM00002 | | | GU | D02202 | B | | | 001-099 |
| 0005 | 08 | HA | | | 15-7 | 29-11-22 | SM00002 | | | GU | D02202 | B | | | 115-199 |
| 0006 | 08 | HA | | | 15-0 | 29-11-22 | SM00003 | | | GU | D02202 | C | | | 001-099 |
| 0006 | 08 | HA | | | 16-0 | 29-11-22 | SM00003 | | | GU | D02202 | C | | | 115-199 |
| 0007 | 20 | HL | | | 81-0 | 29-11-22 | TB0131X | A009 | BJ | | D03400 | 2 | | | 115-199 |
| 0008 | 18 | HL | | | 3-0 | 29-32-21 | D03400 | 1 | | | GD00397 | DC.C | E | | 001-099 |
| 0008 | 18 | HL | | | 1-5 | 29-32-21 | D03400 | 1 | | | GD00397 | DC.. | E | | 115-199 |
| 0009 | 08 | HA | | | 3-0 | 29-11-22 | D02202 | D | | | GD00384 | ST.. | F | | ALL |
| 0010 | 18 | HL | | | 69-0 | 29-32-21 | SP00099 | | 9 | | D03400 | 3 | | | 001-099 |
| 0010 | 18 | HL | | | 66-9 | 29-32-21 | SP00099 | | 9 | | D03400 | 3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2600

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2606 | 286N2606 | | | P31 TO HYD BAY - RIGHT DEMAND PUMP (continued) | | | | | | | | | | |
| YAAB | | | | 0-0 | 29-11-22 | GD00913 | ST.. | E | | GD00384 | ST.. | F | | ALL |
| YAZA | | | | 0-0 | 29-32-21 | GD00913 | ST.. | E | | GD01023 | ST.. | E | | 001-099 |
| YAZA | | | | 0-0 | 29-11-22 | GD00913 | ST.. | E | | GD01023 | ST.. | E | | 115-199 |
| W2608 | 286N2608 | | | P31 TO HYD BAY - CENTER PRIMARY PUMP | | | | | | | | | | |
| 0001 | 04 | 43 | | 84-0 | 29-11-31 | M10006 | A2 | H4 | | SM00001 | | GU | | ALL |
| 0002 | 04 | 43 | | 84-0 | 29-11-31 | M10006 | B2 | H4 | | SM00002 | | GU | | ALL |
| 0003 | 04 | 43 | | 84-0 | 29-11-31 | M10006 | C2 | H4 | | SM00003 | | GU | | ALL |
| 0004 | 08 | HA | | 5-5 | 29-11-31 | SM00001 | | | | D02204 | A | | | ALL |
| 0005 | 08 | HA | | 6-0 | 29-11-31 | SM00002 | | | | D02204 | B | | | ALL |
| 0006 | 08 | HA | | 6-5 | 29-11-31 | SM00003 | | | | D02204 | C | | | ALL |
| 0007 | 20 | HL | | 88-0 | 29-11-31 | TB0131X | B009 | BJ | | D03402 | 2 | | | 115-199 |
| 0008 | 18 | HL | | 5-0 | 29-32-31 | D03402 | 1 | | | GD00549 | DC.C | E | | 001-099 |
| 0008 | 18 | HL | | 3-0 | 29-32-31 | D03402 | 1 | | | GD00549 | DC.C | E | | 115-199 |
| 0009 | 08 | HA | | 2-0 | 29-11-31 | D02204 | D | | | GD00550 | ST.. | F | | ALL |
| 0010 | 18 | HL | | 70-0 | 29-32-31 | SP00554 | | 9 | | D03402 | 3 | | | 001-099 |
| 0010 | 18 | HL | | 73-0 | 29-32-31 | SP00554 | | 9 | | D03402 | 3 | | | 115-199 |
| 0012 | 18 | HL | | 52-0 | 33-31-21 | SP00081 | | 9 | | SP00083 | | 9 | | 001-099 |
| 0012 | 18 | HL | | 48-0 | 33-31-21 | SP00081 | | 9 | | SP00083 | | 9 | | 115-199 |
| 0013 | 18 | HL | | 50-0 | 33-31-21 | SP00083 | | 9 | | S10328 | 2 | C | | 001-099 |
| 0013 | 18 | HL | | 51-0 | 33-31-21 | SP00083 | | 9 | | S10328 | 2 | C | | 115-199 |
| 0014 | 18 | HL | | 13-0 | 33-31-21 | S10328 | 3 | C | | SP00087 | | 9 | | ALL |
| A-AB | | | | 0-0 | 33-31-21 | SP00087 | | 9 | | L00487 | BLK | | | ALL |
| A-AC | | | | 0-0 | 33-31-21 | L00488 | | BLK | | SP00087 | | 9 | | ALL |
| A-AD | | | | 0-0 | 33-31-21 | L00487 | | WHT | | GD02517 | DC.. | E | | ALL |
| A-AE | | | | 0-0 | 33-31-21 | L00488 | | WHT | | GD02517 | DC.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2600

Page 6 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2610 | 286N2610 | | | P32 TO HYD BAY - CENTER DEMAND PUMP | | | | | | | | | | | |
| 0001 | 04 | | 43 | | 91-0 | 29-11-31 | M10022 | A2 | H4 | | SM00001 | | GU | | 001-099 |
| 0001 | 04 | | 43 | | 92-0 | 29-11-31 | M10022 | A2 | H4 | | SM00001 | | GU | | 115-199 |
| 0002 | 04 | | 43 | | 91-0 | 29-11-31 | M10022 | B2 | H4 | | SM00002 | | GU | | 001-099 |
| 0002 | 04 | | 43 | | 92-0 | 29-11-31 | M10022 | B2 | H4 | | SM00002 | | GU | | 115-199 |
| 0003 | 04 | | 43 | | 91-0 | 29-11-31 | M10022 | C2 | H4 | | SM00003 | | GU | | 001-099 |
| 0003 | 04 | | 43 | | 92-0 | 29-11-31 | M10022 | C2 | H4 | | SM00003 | | GU | | 115-199 |
| 0004 | 08 | | HA | | 6-0 | 29-11-31 | SM00001 | | GU | | D02206 | A | | | ALL |
| 0005 | 08 | | HA | | 6-0 | 29-11-31 | SM00002 | | GU | | D02206 | B | | | 001-099 |
| 0005 | 08 | | HA | | 6-5 | 29-11-31 | SM00002 | | GU | | D02206 | B | | | 115-199 |
| 0006 | 08 | | HA | | 7-0 | 29-11-31 | SM00003 | | GU | | D02206 | C | | | ALL |
| 0007 | 20 | | HL | | 96-0 | 29-11-31 | TB0132X | A009 | BJ | | D03404 | 2 | | | 115-199 |
| 0008 | 18 | | HL | | 4-0 | 29-32-31 | D03404 | 1 | | | GD00551 | DC.. | E | | 001-099 |
| 0008 | 18 | | HL | | 3-0 | 29-32-31 | D03404 | 1 | | | GD00551 | DC.C | E | | 115-199 |
| 0009 | 08 | | HA | | 1-8 | 29-11-31 | D02206 | D | | | GD00552 | ST.. | F | | ALL |
| 0010 | 18 | | HL | | 84-0 | 29-32-31 | SP00556 | | 9 | | D03404 | 3 | | | 001-099 |
| 0010 | 18 | | HL | | 82-0 | 29-32-31 | SP00556 | | 9 | | D03404 | 3 | | | 115-199 |
| W2611 | 286N2611 | | | E2-2, E4-1 & E5-2 TO AFT BODY DISCONNECT-CHANNEL RIGHT | | | | | | | | | | | |
| 0001 | 22 | | GA | | 130-0 | 22-11-22 | D40481P | 1 | | | D41693P | 1 | | | 001-099 |
| 0001 | 22 | | GA | | 129-0 | 22-11-22 | D40481P | 1 | | | D41693P | 1 | | | 115-199 |
| 0002 | 22 | | GA | | 130-0 | 22-11-22 | D40481P | 35 | | | D41693P | 17 | | | 001-099 |
| 0002 | 22 | | GA | | 129-0 | 22-11-22 | D40481P | 35 | | | D41693P | 17 | | | 115-199 |
| 0003 | 22 | | GA | | 130-0 | 22-11-22 | D40487J | 24 | | | D41693P | 19 | | | 001-099 |
| 0003 | 22 | | GA | | 129-0 | 22-11-22 | D40487J | 24 | | | D41693P | 19 | | | 115-199 |
| 0004 | 22 | | GA | | 130-0 | 22-11-22 | D40487J | 3 | | | D41693P | 14 | | | 001-099 |
| 0004 | 22 | | GA | | 129-0 | 22-11-22 | D40487J | 3 | | | D41693P | 14 | | | 115-199 |
| 0005Y | 20 | | QB | | 117-0 | 27-41-21 | D41843P | 1 | | | D40699P | 1 | | | 001-099 |
| 0005Y | 20 | | QB | | 118-0 | 27-41-21 | D41843P | 1 | | | D40699P | 1 | | | 115-199 |
| 0006Y | 20 | | QB | | 117-0 | 27-41-21 | D41843P | 2 | | | D40699P | 2 | | | 001-099 |
| 0006Y | 20 | | QB | | 118-0 | 27-41-21 | D41843P | 2 | | | D40699P | 2 | | | 115-199 |
| 0007Y | 22 | | QB | | 117-0 | 27-41-21 | D41843P | 3 | | | D40699P | 3 | | | 001-099 |
| 0007Y | 22 | | QB | | 118-0 | 27-41-21 | D41843P | 3 | | | D40699P | 3 | | | 115-199 |
| 0008Y | 22 | | QB | | 117-0 | 27-41-21 | D41843P | 4 | | | D40699P | 4 | | | 001-099 |
| 0008Y | 22 | | QB | | 118-0 | 27-41-21 | D41843P | 4 | | | D40699P | 4 | | | 115-199 |
| 0009Y | 22 | | QB | | 117-0 | 27-41-21 | D41843P | 5 | | | D40699P | 5 | | | 001-099 |
| 0009Y | 22 | | QB | | 118-0 | 27-41-21 | D41843P | 5 | | | D40699P | 5 | | | 115-199 |
| 0010 | 22 | | GA | | 117-0 | SPARE | D41843P | 6 | | | D40699P | 6 | | | 001-099 |
| 0010 | 22 | | GA | | 118-0 | SPARE | D41843P | 6 | | | D40699P | 6 | | | 115-199 |
| 0016 | 22 | | GA | | 117-0 | 27-48-11 | D40699P | 13 | | | D41843P | 13 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2610

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2611 | 286N2611 | | | E2-2, E4-1 & E5-2 TO AFT BODY DISCONNECT-CHANNEL RIGHT (continued) | | | | | | | | | | | |
| 0016 | 22 | | GA | | 118-0 | 27-48-11 | D40699P | | 13 | | D41843P | | 13 | | 115-199 |
| 0017 | 22 | | GA | | 117-0 | 27-48-11 | D40699P | | 14 | | D41843P | | 14 | | 001-099 |
| 0017 | 22 | | GA | | 118-0 | 27-48-11 | D40699P | | 14 | | D41843P | | 14 | | 115-199 |
| 0018 | 22 | | GA | | 117-0 | 27-48-11 | D40699P | | 15 | | D41843P | | 15 | | 001-099 |
| 0018 | 22 | | GA | | 118-0 | 27-48-11 | D40699P | | 15 | | D41843P | | 15 | | 115-199 |
| 0033 | 22 | | GA | | 130-0 | 27-31-11 | D41693P | | 33 | | D40481P | | 33 | | 001-099 |
| 0033 | 22 | | GA | | 129-0 | 27-31-11 | D41693P | | 33 | | D40481P | | 33 | | 115-199 |
| 2001B | 22 | | GB | AA | 128-0 | 22-11-21 | D40481P | | 3 | | D41693P | | 5 | | 001-099 |
| 2001B | 22 | | GB | AA | 129-0 | 22-11-21 | D40481P | | 3 | | D41693P | | 5 | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 22-11-21 | D40481P | | 4 | | D41693P | | 6 | | ALL |
| 2002B | 22 | | GB | AB | 128-0 | 22-11-21 | D40487J | | 2 | | D41693P | | 7 | | 001-099 |
| 2002B | 22 | | GB | AB | 129-0 | 22-11-21 | D40487J | | 2 | | D41693P | | 7 | | 115-199 |
| 2002R | 22 | | GB | AB | 0-0 | 22-11-21 | D40487J | | 1 | | D41693P | | 8 | | ALL |
| 2003B | 22 | | GB | AC | 128-0 | 22-12-21 | D40481P | | 12 | | D41693P | | 9 | | 001-099 |
| 2003B | 22 | | GB | AC | 129-0 | 22-12-21 | D40481P | | 12 | | D41693P | | 9 | | 115-199 |
| 2003R | 22 | | GB | AC | 0-0 | 22-12-21 | D40481P | | 11 | | D41693P | | 10 | | ALL |
| 2004B | 22 | | GB | AD | 128-0 | 22-13-21 | D40487J | | 6 | | D41693P | | 11 | | 001-099 |
| 2004B | 22 | | GB | AD | 129-0 | 22-13-21 | D40487J | | 6 | | D41693P | | 11 | | 115-199 |
| 2004R | 22 | | GB | AD | 0-0 | 22-13-21 | D40487J | | 16 | | D41693P | | 12 | | ALL |
| 2007B | 24 | | GL | AK | 131-0 | 27-48-21 | D41837P | | 5 | | D40699P | | 12 | | ALL |
| 2007R | 24 | | GL | AK | 0-0 | 27-48-21 | D41837P | | 4 | | D40699P | | 11 | | ALL |
| 2010B | 22 | | GB | AV | 128-0 | 22-11-21 | D41693P | | 35 | | D40481P | | 2 | | 001-099 |
| 2010B | 22 | | GB | AV | 129-0 | 22-11-21 | D41693P | | 35 | | D40481P | | 2 | | 115-199 |
| 2010R | 22 | | GB | AV | 0-0 | 22-11-21 | D41693P | | 34 | | D40481P | | 34 | | ALL |
| 3001B | 22 | | GC | AE | 128-0 | 22-12-21 | D40481P | | 6 | | D41693P | | 13 | | 001-099 |
| 3001B | 22 | | GC | AE | 129-0 | 22-12-21 | D40481P | | 6 | | D41693P | | 13 | | 115-199 |
| 3001R | 22 | | GC | AE | 0-0 | 22-12-21 | D40481P | | 5 | | D41693P | | 4 | | ALL |
| 3001Y | 22 | | GC | AE | 0-0 | 22-12-21 | D40481P | | 7 | | D41693P | | 15 | | ALL |
| 3002B | 22 | | GC | AF | 128-0 | 22-12-21 | D40481P | | 9 | | D41693P | | 16 | | 001-099 |
| 3002B | 22 | | GC | AF | 129-0 | 22-12-21 | D40481P | | 9 | | D41693P | | 16 | | 115-199 |
| 3002R | 22 | | GC | AF | 0-0 | 22-12-21 | D40481P | | 8 | | D41693P | | 2 | | ALL |
| 3002Y | 22 | | GC | AF | 0-0 | 22-12-21 | D40481P | | 10 | | D41693P | | 18 | | ALL |
| 3003B | 22 | | GC | AG | 128-0 | 22-13-21 | D40487J | | 8 | | D41693P | | 3 | | 001-099 |
| 3003B | 22 | | GC | AG | 129-0 | 22-13-21 | D40487J | | 8 | | D41693P | | 3 | | 115-199 |
| 3003R | 22 | | GC | AG | 0-0 | 22-13-21 | D40487J | | 7 | | D41693P | | 20 | | ALL |
| 3003Y | 22 | | GC | AG | 0-0 | 22-13-21 | D40487J | | 9 | | D41693P | | 21 | | ALL |
| 3004B | 22 | | GC | AH | 128-0 | 22-13-21 | D40487J | | 12 | | D41693P | | 22 | | 001-099 |
| 3004B | 22 | | GC | AH | 129-0 | 22-13-21 | D40487J | | 12 | | D41693P | | 22 | | 115-199 |
| 3004R | 22 | | GC | AH | 0-0 | 22-13-21 | D40487J | | 11 | | D41693P | | 23 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2610

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|-------------|---------|---------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | | |
| W2611 | 286N2611 | | | | E2-2, E4-1 & E5-2 TO AFT BODY DISCONNECT-CHANNEL RIGHT (continued) | | | | | | | | | | | | |
| 3004Y | 22 | GC | AH | | 0-0 | 22-13-21 | D40487J | 13 | | | | D41693P | 24 | | ALL | | |
| 3005B | 22 | GC | AL | | 128-0 | 22-13-21 | D41693P | 27 | | | | D40487J | 18 | | 001-099 | | |
| 3005B | 22 | GC | AL | | 129-0 | 22-13-21 | D41693P | 27 | | | | D40487J | 18 | | 115-199 | | |
| 3005R | 22 | GC | AL | | 0-0 | 22-13-21 | D41693P | 26 | | | | D40487J | 17 | | ALL | | |
| 3005Y | 22 | GC | AL | | 0-0 | 22-13-21 | D41693P | 28 | | | | D40487J | 19 | | ALL | | |
| 3007B | 24 | GM | AJ | | 131-0 | 27-48-21 | D41837P | 2 | | | | D40699P | 9 | | ALL | | |
| 3007R | 24 | GM | AJ | | 0-0 | 27-48-21 | D41837P | 1 | | | | D40699P | 8 | | ALL | | |
| 3007Y | 24 | GM | AJ | | 0-0 | 27-48-21 | D41837P | 3 | | | | D40699P | 10 | | ALL | | |
| 3009B | 22 | GC | AM | | 128-0 | 22-12-21 | D41693P | 37 | | | | D40481P | 37 | | 001-099 | | |
| 3009B | 22 | GC | AM | | 129-0 | 22-12-21 | D41693P | 37 | | | | D40481P | 37 | | 115-199 | | |
| 3009R | 22 | GC | AM | | 0-0 | 22-12-21 | D41693P | 36 | | | | D40481P | 36 | | ALL | | |
| 3009Y | 22 | GC | AM | | 0-0 | 22-12-21 | D41693P | 38 | | | | D40481P | 38 | | ALL | | |
| 3010B | 22 | GC | AN | | 128-0 | 22-12-21 | D41693P | 40 | | | | D40481P | 30 | | 001-099 | | |
| 3010B | 22 | GC | AN | | 129-0 | 22-12-21 | D41693P | 40 | | | | D40481P | 30 | | 115-199 | | |
| 3010R | 22 | GC | AN | | 0-0 | 22-12-21 | D41693P | 39 | | | | D40481P | 29 | | ALL | | |
| 3010Y | 22 | GC | AN | | 0-0 | 22-12-21 | D41693P | 41 | | | | D40481P | 31 | | ALL | | |
| W2612 | 286N2612 | | | | AFT CARGO BAY TO CENTER DEMAND HYD PUMP PRESS. SW. | | | | | | | | | | | | |
| 0001 | 18 | GA | | | 4-0 | 29-11-31 | D02924 | 2 | | | | GD00553 | DC.. | E | | ALL | |
| 0002 | 20 | GA | | | 109-0 | 29-11-31 | D02924 | 3 | | | | D40214P | 1 | | | 001-099 | |
| 0002 | 20 | GA | | | 119-0 | 29-11-31 | D02924 | 3 | | | | D40214P | 1 | | | 115-199 | |
| 0003 | 18 | GA | | | 4-0 | 29-11-31 | D02928 | 2 | | | | GD00553 | DC.. | E | | ALL | |
| 0004 | 20 | GA | | | 109-0 | 29-11-31 | D02928 | 3 | | | | D40214P | 2 | | | 001-099 | |
| 0004 | 20 | GA | | | 119-0 | 29-11-31 | D02928 | 3 | | | | D40214P | 2 | | | 115-199 | |
| 0005 | 18 | GA | | | 4-0 | 29-11-31 | D02926 | 2 | | | | GD00553 | DC.. | E | | ALL | |
| 0006 | 20 | GA | | | 110-0 | 29-11-31 | D02926 | 3 | | | | D40214P | 3 | | | 001-099 | |
| 0006 | 20 | GA | | | 119-0 | 29-11-31 | D02926 | 3 | | | | D40214P | 3 | | | 115-199 | |
| 0007 | 20 | GA | | | 109-0 | 29-11-31 | D02924 | 1 | | | | D40214P | 4 | | | 001-099 | |
| 0007 | 20 | GA | | | 119-0 | 29-11-31 | D02924 | 1 | | | | D40214P | 4 | | | 115-199 | |
| W2613 | 286N2613 | | | | RANUAL STABILIZER TRIM-ALTERNATE CONTROL | | | | | | | | | | | | |
| 0001Y | 20 | QB | | | 10-0 | 27-41-31 | D01825 | 3 | | | | SP00397 | | 9 | | ALL | |
| 0002Y | 20 | QB | | | 10-0 | 27-41-31 | D01825 | 11 | | | | SP00399 | | 9 | | 001-099 | |
| 0002Y | 20 | QB | | | 10-0 | 27-41-31 | D01825 | 11 | | | | SP00397 | | 9 | | 115-199 | |
| 0003Y | 20 | QB | | | 4-0 | 27-41-31 | D01825 | 9 | | | | GD02316 | DC.. | 2 | | 001-099 | |
| 0003Y | 20 | QB | | | 6-0 | 27-41-31 | D01825 | 9 | | | | GD02316 | DC.. | 2 | | 115-199 | |
| 2501B | 20 | H5 | A | | 133-0 | 27-41-31 | D41335P | 2 | | | | D01825 | | 6 | | 001-099 | |
| 2501B | 20 | H5 | A | | 134-0 | 27-41-31 | D41335P | 2 | | | | D01825 | | 6 | | 115-199 | |
| 2501R | 20 | H5 | A | | 0-0 | 27-41-31 | D41335P | 1 | | | | D01825 | | 7 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2610

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| Wire No. | | | | | | | | | | | | | | | | |
| W2613 | 286N2613 | | | | RANUAL STABILIZER TRIM-ALTERNATE CONTROL (continued) | | | | | | | | | | | |
| 2501Z | | | | A | 0-0 | 27-41-31 | D41335P | DED | | | D01825 | DED | | | ALL | |
| 2502B | 20 | H5 | | B | 133-0 | 27-41-31 | D41227P | 2 | | | D01825 | 4 | | | 001-099 | |
| 2502B | 20 | H5 | | B | 134-0 | 27-41-31 | D41227P | 2 | | | D01825 | 4 | | | 115-199 | |
| 2502R | 20 | H5 | | B | 0-0 | 27-41-31 | D41227P | 1 | | | D01825 | 12 | | | ALL | |
| 2502Z | | | | B | 0-0 | 27-41-31 | D41227P | DED | | | D01825 | DED | | | ALL | |
| 2503B | 20 | H5 | | C | 133-0 | SPARE | D41227P | 4 | | | D01825 | 2 | | | 001-099 | |
| 2503B | 20 | H5 | | C | 134-0 | SPARE | D41227P | 4 | | | D01825 | 2 | | | 115-199 | |
| 2503R | 20 | H5 | | C | 0-0 | SPARE | D41227P | 3 | | | D01825 | 1 | | | ALL | |
| 2503Z | | | | C | 0-0 | SPARE | D41227P | DED | | | D01825 | DED | | | ALL | |
| W2615 | 286N2615 | | | | MANUAL STABILIZER TRIM-ALTERNATE CONTROL | | | | | | | | | | | |
| 0004Y | 20 | QB | | | 11-0 | 27-41-31 | D01827 | 10 | | | TB0100X | D002 | BJ | | ALL | |
| 2501B | 20 | H5 | | A | 135-0 | 27-41-31 | D41337P | 2 | | | D01827 | 6 | | | ALL | |
| 2501R | 20 | H5 | | A | 0-0 | 27-41-31 | D41337P | 1 | | | D01827 | 7 | | | ALL | |
| 2501Z | | | | A | 0-0 | 27-41-31 | D41337P | DED | | | D01827 | DED | | | ALL | |
| 2502B | 20 | H5 | | B | 135-0 | 27-41-31 | D41225P | 2 | | | D01827 | 4 | | | ALL | |
| 2502R | 20 | H5 | | B | 0-0 | 27-41-31 | D41225P | 1 | | | D01827 | 12 | | | ALL | |
| 2502Z | | | | B | 0-0 | 27-41-31 | D41225P | DED | | | D01827 | DED | | | ALL | |
| 2503B | 20 | H5 | | C | 135-0 | SPARE | D41225P | 4 | | | D01827 | 5 | | | ALL | |
| 2503R | 20 | H5 | | C | 0-0 | SPARE | D41225P | 3 | | | D01827 | 3 | | | ALL | |
| 2503Z | | | | C | 0-0 | SPARE | D41225P | DED | | | D01827 | DED | | | ALL | |
| W2617 | 286N2617 | | | | E4-1 TO AFT BODY DISCONNECT - CHANNEL RA | | | | | | | | | | | |
| 0001 | 18 | GA | | | 117-0 | 22-21-21 | D41793P | 21 | | | D40489J | 21 | | | ALL | |
| 0002Y | 22 | QB | | | 117-0 | 27-41-21 | D41793P | 27 | | | D40959P | 1 | | | 001-099 | |
| 0002Y | 22 | QB | | | 116-0 | 27-41-21 | D41793P | 27 | | | D40959P | 1 | | | 115-199 | |
| 0003Y | 22 | QB | | | 117-0 | 27-41-21 | D41793P | 26 | | | D40959P | 2 | | | 001-099 | |
| 0003Y | 22 | QB | | | 116-0 | 27-41-21 | D41793P | 26 | | | D40959P | 2 | | | 115-199 | |
| 0004 | 22 | GA | | | 117-0 | 27-41-21 | D41793P | 28 | | | D40959P | 3 | | | 001-099 | |
| 0004 | 22 | GA | | | 116-0 | 27-41-21 | D41793P | 28 | | | D40959P | 3 | | | 115-199 | |
| 0005Y | 22 | QB | | | 117-0 | 27-41-21 | D41793P | 37 | | | D40959P | 4 | | | 001-099 | |
| 0005Y | 22 | QB | | | 116-0 | 27-41-21 | D41793P | 37 | | | D40959P | 4 | | | 115-199 | |
| 0006 | 22 | GA | | | 117-0 | 27-41-21 | D41793P | 38 | | | D40959P | 6 | | | 001-099 | |
| 0006 | 22 | GA | | | 116-0 | 27-41-21 | D41793P | 38 | | | D40959P | 6 | | | 115-199 | |
| 2001B | 22 | GB | AA | | 117-0 | 27-21-22 | D41793P | 2 | | | D40489J | 2 | | | ALL | |
| 2001R | 22 | GB | AA | | 0-0 | 27-21-22 | D41793P | 1 | | | D40489J | 1 | | | ALL | |
| 2002B | 22 | GB | AC | | 117-0 | 27-21-22 | D41793P | 7 | | | D40489J | 7 | | | ALL | |
| 2002R | 22 | GB | AC | | 0-0 | 27-21-22 | D41793P | 6 | | | D40489J | 6 | | | ALL | |
| 2003B | 22 | GB | AD | | 117-0 | 22-21-21 | D41793P | 9 | | | D40489J | 9 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2610

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2617 | 286N2617 | | | E4-1 TO AFT BODY DISCONNECT - CHANNEL RA (continued) | | | | | | | | | | | |
| 2003R | 22 | | GB | AD | 0-0 | 22-21-21 | D41793P | | 8 | | D40489J | | 8 | | ALL |
| 2004B | 22 | | GB | AF | 117-0 | 22-21-21 | D41793P | | 14 | | D40489J | | 14 | | ALL |
| 2004R | 22 | | GB | AF | 0-0 | 22-21-21 | D41793P | | 13 | | D40489J | | 13 | | ALL |
| 2005B | 22 | | GB | AG | 117-0 | 27-21-22 | D41793P | | 31 | | D40489J | | 18 | | ALL |
| 2005R | 22 | | GB | AG | 0-0 | 27-21-22 | D41793P | | 30 | | D40489J | | 17 | | ALL |
| 2006B | 22 | | GB | AH | 117-0 | 27-21-22 | D41793P | | 33 | | D40489J | | 20 | | ALL |
| 2006R | 22 | | GB | AH | 0-0 | 27-21-22 | D41793P | | 32 | | D40489J | | 19 | | ALL |
| 2007B | 22 | | GB | AJ | 117-0 | 22-21-21 | D41793P | | 36 | | D40489J | | 25 | | ALL |
| 2007R | 22 | | GB | AJ | 0-0 | 22-21-21 | D41793P | | 35 | | D40489J | | 24 | | ALL |
| 3001B | 22 | | GC | AB | 117-0 | 27-21-22 | D41793P | | 4 | | D40489J | | 4 | | ALL |
| 3001R | 22 | | GC | AB | 0-0 | 27-21-22 | D41793P | | 3 | | D40489J | | 3 | | ALL |
| 3001Y | 22 | | GC | AB | 0-0 | 27-21-22 | D41793P | | 5 | | D40489J | | 5 | | ALL |
| 3002B | 22 | | GC | AE | 117-0 | 22-21-21 | D41793P | | 11 | | D40489J | | 11 | | ALL |
| 3002R | 22 | | GC | AE | 0-0 | 22-21-21 | D41793P | | 10 | | D40489J | | 10 | | ALL |
| 3002Y | 22 | | GC | AE | 0-0 | 22-21-21 | D41793P | | 12 | | D40489J | | 12 | | ALL |
| W2619 | 286N2619 | | | VHF-C COAX, ANT DISC. TO ANT. | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-12-31 | D41029P | = C1 | | | D00169 | = C1 | | | 001-099 |
| 001CX | | | BS | AA | 5-0 | 23-12-31 | D41029P | = A1 | | | D00169 | = A1 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2610

Page 5 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2621 | 286N2621 | | | E2-3 TO AFT BODY DISCONNECT-CHANNEL CENTER | | | | | | | | | | | |
| 0001 | 22 | | GA | | 133-0 | 22-11-32 | D41695P | | 1 | | D40497P | | 1 | | ALL |
| 0002 | 22 | | GA | | 133-0 | 22-11-32 | D41695P | | 17 | | D40497P | | 14 | | ALL |
| 0003 | 22 | | GA | | 133-0 | 22-11-32 | D41695P | | 19 | | D40473J | | 24 | | ALL |
| 0004 | 22 | | GA | | 133-0 | 22-11-32 | D41695P | | 14 | | D40473J | | 3 | | ALL |
| 0025 | 22 | | GA | | 133-0 | 31-51-41 | D41695P | | 25 | | D40497P | | 25 | | ALL |
| 0026 | 22 | | GA | | 133-0 | 27-23-11 | D41695P | | 26 | | D40497P | | 26 | | ALL |
| 0027 | 22 | | GA | | 133-0 | 27-23-11 | D41695P | | 27 | | D40497P | | 27 | | ALL |
| 2001B | 22 | | GB | AA | 133-0 | 22-11-31 | D41695P | | 5 | | D40497P | | 3 | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 22-11-31 | D41695P | | 6 | | D40497P | | 4 | | ALL |
| 2002B | 22 | | GB | AB | 133-0 | 22-11-31 | D41695P | | 7 | | D40473J | | 2 | | ALL |
| 2002R | 22 | | GB | AB | 0-0 | 22-11-31 | D41695P | | 8 | | D40473J | | 1 | | ALL |
| 2003B | 22 | | GB | AF | 133-0 | 22-12-31 | D41695P | | 9 | | D40497P | | 12 | | ALL |
| 2003R | 22 | | GB | AF | 0-0 | 22-12-31 | D41695P | | 10 | | D40497P | | 11 | | ALL |
| 2004B | 22 | | GB | AG | 133-0 | 22-13-31 | D41695P | | 11 | | D40473J | | 6 | | ALL |
| 2004R | 22 | | GB | AG | 0-0 | 22-13-31 | D41695P | | 12 | | D40473J | | 16 | | ALL |
| 2007B | 24 | | GL | AK | 134-0 | 27-48-21 | D41839P | | 5 | | D40497P | | 17 | | 001-099 |
| 2007B | 24 | | GL | AK | 136-0 | 27-48-21 | D41839P | | 5 | | D40497P | | 17 | | 115-199 |
| 2007R | 24 | | GL | AK | 0-0 | 27-48-21 | D41839P | | 4 | | D40497P | | 16 | | ALL |
| 2010B | 22 | | GB | AV | 133-0 | 22-11-31 | D41695P | | 35 | | D40497P | | 35 | | ALL |
| 2010R | 22 | | GB | AV | 0-0 | 22-11-31 | D41695P | | 34 | | D40497P | | 34 | | ALL |
| 3001B | 22 | | GC | AC | 133-0 | 22-12-31 | D41695P | | 13 | | D40497P | | 6 | | ALL |
| 3001R | 22 | | GC | AC | 0-0 | 22-12-31 | D41695P | | 4 | | D40497P | | 5 | | ALL |
| 3001Y | 22 | | GC | AC | 0-0 | 22-12-31 | D41695P | | 15 | | D40497P | | 7 | | ALL |
| 3002B | 22 | | GC | AD | 133-0 | 22-12-31 | D41695P | | 16 | | D40497P | | 9 | | ALL |
| 3002R | 22 | | GC | AD | 0-0 | 22-12-31 | D41695P | | 2 | | D40497P | | 8 | | ALL |
| 3002Y | 22 | | GC | AD | 0-0 | 22-12-31 | D41695P | | 18 | | D40497P | | 10 | | ALL |
| 3003B | 22 | | GC | AE | 133-0 | 22-13-31 | D41695P | | 3 | | D40473J | | 8 | | ALL |
| 3003R | 22 | | GC | AE | 0-0 | 22-13-31 | D41695P | | 20 | | D40473J | | 7 | | ALL |
| 3003Y | 22 | | GC | AE | 0-0 | 22-13-31 | D41695P | | 21 | | D40473J | | 9 | | ALL |
| 3004B | 22 | | GC | AH | 133-0 | 22-13-31 | D41695P | | 22 | | D40473J | | 12 | | ALL |
| 3004R | 22 | | GC | AH | 0-0 | 22-13-31 | D41695P | | 23 | | D40473J | | 11 | | ALL |
| 3004Y | 22 | | GC | AH | 0-0 | 22-13-31 | D41695P | | 24 | | D40473J | | 13 | | ALL |
| 3007B | 24 | | GM | AJ | 134-0 | 27-48-21 | D41839P | | 2 | | D40497P | | 2 | | 001-099 |
| 3007B | 24 | | GM | AJ | 136-0 | 27-48-21 | D41839P | | 2 | | D40497P | | 2 | | 115-199 |
| 3007R | 24 | | GM | AJ | 0-0 | 27-48-21 | D41839P | | 1 | | D40497P | | 13 | | ALL |
| 3007Y | 24 | | GM | AJ | 0-0 | 27-48-21 | D41839P | | 3 | | D40497P | | 15 | | ALL |
| 3009B | 22 | | GC | AN | 133-0 | 22-12-31 | D41695P | | 37 | | D40497P | | 37 | | ALL |
| 3009R | 22 | | GC | AN | 0-0 | 22-12-31 | D41695P | | 36 | | D40497P | | 36 | | ALL |
| 3009Y | 22 | | GC | AN | 0-0 | 22-12-31 | D41695P | | 38 | | D40497P | | 38 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2620

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2621 | 286N2621 | | | | E2-3 TO AFT BODY DISCONNECT-CHANNEL CENTER (continued) | | | | | | | | | | |
| 3010B | 22 | GC | AP | | 133-0 | SPARE | D41695P | 40 | | | D40497P | 40 | | | ALL |
| 3010R | 22 | GC | AP | | 0-0 | SPARE | D41695P | 39 | | | D40497P | 39 | | | ALL |
| 3010Y | 22 | GC | AP | | 0-0 | SPARE | D41695P | 41 | | | D40497P | 41 | | | ALL |
| W2626 | 286N2626 | | | | P54 TO SECT. 46- DUCT LEAK DET. AND APU FIRE DET. | | | | | | | | | | |
| 0001 | 18 | HA | | | 132-0 | 26-18-11 | D40218P | 1 | 18 | | D41250P | 1 | | | 001-099 |
| 0001 | 18 | HA | | | 143-0 | 26-18-11 | D40218P | 1 | 18 | | D01970 | = 1 | | | 115-199 |
| 0002 | 18 | HA | | | 110-0 | 26-18-11 | D40218P | 8 | 18 | | D01972 | = 1 | | | 001-099 |
| 0002 | 18 | HA | | | 113-0 | 26-18-11 | D40218P | 8 | 18 | | D01972 | = 1 | | | 115-199 |
| 0003 | 18 | HA | | | 132-0 | 26-18-11 | D40218P | 22 | 18 | | D41250P | 3 | | | 001-099 |
| 0003 | 18 | HA | | | 143-0 | 26-18-11 | D40218P | 22 | 18 | | D01974 | = 1 | | | 115-199 |
| 0004 | 18 | HA | | | 110-0 | 26-18-11 | D40218P | 24 | 18 | | D01976 | = 1 | | | 001-099 |
| 0004 | 18 | HA | | | 113-0 | 26-18-11 | D40218P | 24 | 18 | | D01976 | = 1 | | | 115-199 |
| 0005 | 18 | HA | | | 132-0 | 26-18-11 | D40218P | 26 | 18 | | D41250P | 5 | | | 001-099 |
| 0005 | 18 | HA | | | 146-0 | 26-18-11 | D40218P | 26 | 18 | | D01978 | = 1 | | | 115-199 |
| 0006 | 18 | HA | | | 132-0 | 26-18-11 | D40218P | 28 | 18 | | D41250P | 6 | | | 001-099 |
| 0006 | 18 | HA | | | 169-0 | 26-18-11 | D40218P | 28 | 18 | | D01980 | = 1 | | | 115-199 |
| 0007 | 18 | HA | | | 132-0 | 26-18-11 | D40218P | 30 | 18 | | D41250P | 7 | | | 001-099 |
| 0007 | 18 | HA | | | 146-0 | 26-18-11 | D40218P | 30 | 18 | | D01982 | = 1 | | | 115-199 |
| 0008 | 18 | HA | | | 132-0 | 26-18-11 | D40218P | 32 | 18 | | D41250P | 8 | | | 001-099 |
| 0008 | 18 | HA | | | 169-0 | 26-18-11 | D40218P | 32 | 18 | | D01984 | = 1 | | | 115-199 |
| 0009R | 22 | QA | | | 132-0 | 26-15-11 | D40218P | 9 | | | D41250P | 12 | | | 001-099 |
| 0009R | 20 | QA | | | 170-0 | 26-15-11 | D40218P | 9 | | | D40316J | 4 | | | 115-199 |
| 0010R | 22 | QA | | | 134-0 | 26-15-11 | D40218P | 10 | | | D41250P | 13 | | | 001-099 |
| 0010R | 20 | QA | | | 10-0 | 26-15-11 | GD01607 | DC.. | E | | D40316J | 2 | | | 115-199 |
| 0011R | 22 | QA | | | 132-0 | 26-15-11 | D40218P | 11 | | | D41250P | 11 | | | 001-099 |
| 0011R | 20 | QA | | | 170-0 | 26-15-11 | D40218P | 11 | | | D40316J | 6 | | | 115-199 |
| 0012 | 20 | GA | | | 129-0 | SPARE | D40218P | 12 | | | D41062P | 2 | | | 001-099 |
| 0012 | 20 | GA | | | 146-0 | SPARE | D40218P | 12 | | | D41062P | 2 | | | 115-199 |
| 0014R | 22 | QA | | | 132-0 | SPARE | D40218P | 14 | | | D41250P | 14 | | | 001-099 |
| 0015 | 20 | GA | | | 129-0 | 28-25-21 | D40218P | 15 | | | D41062P | 1 | | | 001-099 |
| 0015 | 20 | GA | | | 146-0 | 28-25-21 | D40218P | 15 | | | D41062P | 1 | | | 115-199 |
| 0016 | 20 | GA | | | 129-0 | SPARE | D40218P | 16 | | | D41062P | 5 | | | 001-099 |
| 0016 | 20 | GA | | | 146-0 | SPARE | D40218P | 16 | | | D41062P | 5 | | | 115-199 |
| 0017 | 20 | GA | | | 143-0 | 21-31-31 | D02338 | 2 | | | SP00496 | 9 | | | 001-099 |
| 0017 | 20 | GA | | | 142-0 | 21-31-31 | D02338 | 2 | | | SP00496 | 9 | | | 115-199 |
| 0018 | 20 | GA | | | 143-0 | 21-31-31 | D02338 | 1 | | | SP00498 | 9 | | | 001-099 |
| 0018 | 20 | GA | | | 142-0 | 21-31-31 | D02338 | 1 | | | SP00498 | 9 | | | 115-199 |
| 0019 | 20 | GA | | | 5-0 | 21-31-31 | D02338 | 3 | | | GD01579 | DC.. | E | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2620

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2626 | 286N2626 | | | | P54 TO SECT. 46- DUCT LEAK DET. AND APU FIRE DET. (continued) | | | | | | | | | | | | |
| 0019 | 20 | | GA | | 3-0 | 21-31-31 | | D02338 | | 3 | | GD01579 | DC.. | E | | 115-199 | |
| 0020 | 20 | | GA | | 132-0 | 26-22-21 | | D41250P | | 9 | | D40218P | 17 | | | 001-099 | |
| 0020 | 20 | | GA | | 175-0 | 26-22-21 | | D02262 | | 1 | | D40218P | 17 | | | 115-199 | |
| 0021 | 20 | | GA | | 7-0 | 26-22-21 | | D02262 | | 2 | | GD01607 | DC.. | E | | 115-199 | |
| 0022 | 20 | | GA | | 7-0 | 26-22-21 | | D02262 | | 3 | | GD01608 | ST.. | E | | 115-199 | |
| 0023 | 20 | | GA | | 132-0 | 26-22-21 | | D41250P | | 10 | | D40218P | 18 | | | 001-099 | |
| 0023 | 20 | | GA | | 173-0 | 26-22-21 | | D02264 | | 1 | | D40218P | 18 | | | 115-199 | |
| 0024 | 20 | | GA | | 8-0 | 26-22-21 | | D02264 | | 3 | | GD01607 | DC.. | E | | 115-199 | |
| 0025 | 20 | | GA | | 110-6 | 26-21-11 | | D40218P | | 19 | | D42148P | 8 | | | 001-099 | |
| 0025 | 20 | | GA | | 113-0 | 26-21-11 | | D40218P | | 19 | | D42148P | 8 | | | 115-199 | |
| 0026 | 20 | | GA | | 2-0 | 26-21-11 | | D02186 | | 3 | | GD01789 | DC.. | E | | ALL | |
| 0027 | 20 | | GA | | 110-6 | 26-21-11 | | D40218P | | 20 | | D42148P | 4 | | | 001-099 | |
| 0027 | 20 | | GA | | 113-0 | 26-21-11 | | D40218P | | 20 | | D42148P | 4 | | | 115-199 | |
| 0028 | 20 | | GA | | 3-0 | 26-21-11 | | D42148P | | 5 | | GD01788 | DC.. | E | | ALL | |
| 0029 | 20 | | GA | | 3-0 | 26-21-11 | | D42148P | | 6 | | GD01787 | ST.. | E | | ALL | |
| 0030 | 20 | | GA | | 110-6 | 26-21-11 | | D40218P | | 21 | | D42148P | 1 | | | 001-099 | |
| 0030 | 20 | | GA | | 113-0 | 26-21-11 | | D40218P | | 21 | | D42148P | 1 | | | 115-199 | |
| 0031 | 20 | | GA | | 3-0 | 26-21-11 | | D42148P | | 2 | | GD01788 | DC.. | E | | ALL | |
| 0032 | 20 | | GA | | 3-0 | 26-21-11 | | D42148P | | 3 | | GD01787 | ST.. | E | | ALL | |
| 0033 | 22 | | GA | | 117-0 | 26-16-11 | | D41266J | | 4 | | D40218P | 33 | | | 001-099 | |
| 0033 | 22 | | GA | | 118-0 | 26-16-11 | | D04406 | | 4 | | D40218P | 33 | | | 115-199 | |
| 0034 | 22 | | GA | | 117-0 | 26-16-11 | | D41266J | | 12 | | D40218P | 34 | | | 001-099 | |
| 0034 | 22 | | GA | | 118-0 | 26-16-11 | | D04406 | | 12 | | D40218P | 34 | | | 115-199 | |
| 0035 | 22 | | GA | | 117-0 | 26-16-11 | | D41266J | | 11 | | D40218P | 35 | | | 001-099 | |
| 0035 | 22 | | GA | | 118-0 | 26-16-11 | | D04406 | | 11 | | D40218P | 35 | | | 115-199 | |
| 0036 | 22 | | GA | | 4-0 | 26-16-11 | | D41266J | | 5 | | GD02244 | DC.. | E | | 001-099 | |
| 0036 | 22 | | GA | | 4-0 | 26-16-11 | | D04406 | | 5 | | GD02244 | DC.. | E | | 115-199 | |
| 0037 | 22 | | GA | | 4-0 | 26-16-11 | | D41266J | | 9 | | GD02244 | DC.. | E | | 001-099 | |
| 0037 | 22 | | GA | | 4-0 | 26-16-11 | | D04406 | | 9 | | GD02244 | DC.. | E | | 115-199 | |
| 0038 | 22 | | GA | | 117-0 | 26-16-11 | | D04408 | | 4 | | D40218P | 36 | | | 001-099 | |
| 0038 | 22 | | GA | | 119-0 | 26-16-11 | | D04408 | | 4 | | D40218P | 36 | | | 115-199 | |
| 0039 | 22 | | GA | | 117-0 | 26-16-11 | | D04408 | | 12 | | D40218P | 37 | | | 001-099 | |
| 0039 | 22 | | GA | | 118-0 | 26-16-11 | | D04408 | | 12 | | D40218P | 37 | | | 115-199 | |
| 0040 | 22 | | GA | | 117-0 | 26-16-11 | | D04408 | | 11 | | D40218P | 38 | | | 001-099 | |
| 0040 | 22 | | GA | | 118-0 | 26-16-11 | | D04408 | | 11 | | D40218P | 38 | | | 115-199 | |
| 0041 | 22 | | GA | | 4-0 | 26-16-11 | | D04408 | | 5 | | GD02244 | DC.. | E | | ALL | |
| 0042 | 22 | | GA | | 4-0 | 26-16-11 | | D04408 | | 9 | | GD02244 | DC.. | E | | ALL | |
| 0043 | 20 | | GA | | 3-0 | 26-23-11 | | D04410 | | 1 | | GD02289 | ST.. | E | | ALL | |
| 0044 | 20 | | GA | | 106-6 | 26-23-11 | | SM00002 | | 9 | | D40218P | 44 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W2620

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2626 | 286N2626 | | | P54 TO SECT. 46- DUCT LEAK DET. AND APU FIRE DET. (continued) | | | | | | | | | | | |
| 0044 | 20 | | GA | | 109-0 | 26-23-11 | D40218P | 44 | | | SM00002 | | 9 | | 115-199 |
| 0045 | 20 | | GA | | 3-0 | 26-23-11 | D04410 | 3 | | | GD02290 | DC.. | E | | 001-099 |
| 0045 | 20 | | GA | | 4-0 | 26-23-11 | D04410 | 3 | | | GD02290 | DC.. | E | | 115-199 |
| 0046 | 20 | | GA | | 3-0 | 26-23-11 | D42144P | | | FA | GD02250 | ST.. | E | | 001-099 |
| 0046 | 20 | | GA | | 2-0 | 26-23-11 | D42144P | | | FA | GD02250 | ST.. | E | | 115-199 |
| 0047 | 20 | | GA | | 3-0 | 26-23-11 | D42144P | 3 | | | GD02250 | ST.. | E | | 001-099 |
| 0047 | 20 | | GA | | 2-0 | 26-23-11 | D42144P | 3 | | | GD02250 | ST.. | E | | 115-199 |
| 0048 | 20 | | GA | | 2-0 | 26-23-11 | D42144P | 2 | | | GD02251 | DC.. | E | | ALL |
| 0049 | 20 | | GA | | 106-6 | 26-23-11 | D42144P | 4 | | | D40218P | 45 | | | 001-099 |
| 0049 | 20 | | GA | | 109-0 | 26-23-11 | D42144P | 4 | | | D40218P | 45 | | | 115-199 |
| 0050 | 20 | | GA | | 3-0 | 26-23-11 | D42144P | 6 | | | GD02250 | ST.. | E | | 001-099 |
| 0050 | 20 | | GA | | 2-0 | 26-23-11 | D42144P | 6 | | | GD02250 | ST.. | E | | 115-199 |
| 0051 | 20 | | GA | | 2-0 | 26-23-11 | D42144P | 5 | | | GD02251 | DC.. | E | | ALL |
| 0052 | 20 | | GA | | 89-0 | 28-22-21 | D40902P | 1 | | | D40218P | 2 | | | 001-099 |
| 0052 | 20 | | GA | | 89-0 | 28-22-21 | D40902J | 1 | | | D40218P | 2 | | | 115-199 |
| 0053 | 20 | | GA | | 89-0 | 28-22-21 | D40902P | 3 | | | D40218P | 5 | | | 001-099 |
| 0053 | 20 | | GA | | 89-0 | 28-22-21 | D40902J | 3 | | | D40218P | 5 | | | 115-199 |
| 0054 | 20 | | GA | | 89-0 | 28-22-21 | D40902P | 2 | | | D40218P | 25 | | | 001-099 |
| 0054 | 20 | | GA | | 89-0 | 28-22-21 | D40902J | 2 | | | D40218P | 25 | | | 115-199 |
| 0055 | 20 | | GA | | 89-0 | 28-25-11 | D40218P | 6 | | | D40902P | 4 | | | 001-099 |
| 0055 | 20 | | GA | | 89-0 | 28-25-11 | D40218P | 6 | | | D40902J | 4 | | | 115-199 |
| 0056 | 20 | | GA | | 21-0 | 26-23-11 | D10656 | 2 | | | SM00002 | | 9 | | 001-099 |
| 0056 | 20 | | GA | | 21-0 | 26-23-11 | SM00002 | | 9 | | D10656 | 2 | | | 115-199 |
| 0057 | 20 | | GA | | 3-0 | 26-23-11 | D10656 | 3 | | | GD02755 | DC.. | E | | 001-099 |
| 0057 | 20 | | GA | | 2-0 | 26-23-11 | D10656 | 3 | | | GD02755 | DC.. | E | | 115-199 |
| 0059 | 20 | | GA | | 3-0 | 26-21-11 | D42148P | 7 | | | D02186 | 1 | | | ALL |
| 0060 | 20 | | GA | | 2-0 | 26-21-11 | D02186 | 4 | | | GD01787 | ST.. | E | | ALL |
| 0061 | 20 | | GA | | 8-0 | 26-22-21 | D02264 | 4 | | | GD01608 | ST.. | E | | 115-199 |
| 0067 | 20 | | GA | | 1-0 | 26-23-11 | SM00002 | | 9 | | D42144P | 8 | | | ALL |
| 0068 | 20 | | GA | | 4-0 | 26-23-11 | D42144P | 7 | | | D04410 | 2 | | | ALL |
| 1001 | 20 | | GT | AA | 106-6 | 26-23-11 | D42144P | 1 | | | D40218P | 43 | | | 001-099 |
| 1001 | 20 | | GT | AA | 109-0 | 26-23-11 | D42144P | 1 | | | D40218P | 43 | | | 115-199 |
| 1001Z | | | | AA | 0-0 | 26-23-11 | D42144P | | | FA | D40218P | DED | | | ALL |
| YAAA | | | | | 0-0 | 28-22-21 | D40902P | S/R | | | GD02743 | ST.. | E | | 001-099 |
| YAAA | | | | | 0-0 | 28-22-21 | D40902J | S/R | | | GD02743 | ST.. | E | | 115-199 |
| W2628 | 286N2628 | | | P54 TO SEC. 46- E6 RELAY PNL, R. FIRE EXT. BOTTLE AND APU FIREWALL | | | | | | | | | | | |
| 0001R | 22 | | QA | | 124-4 | 26-15-11 | D40220P | 1 | | | D41254P | 1 | | | 001-099 |
| 0001R | 20 | | QA | | 154-0 | 26-15-11 | D40220P | 1 | | | D40318J | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2620

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2628 | 286N2628 | | | | P54 TO SEC. 46- E6 RELAY PNL, R. FIRE EXT. BOTTLE AND APU FIREWALL (continued) | | | | | | | | | | | |
| 0002R | 22 | | QA | | 124-4 | 26-15-11 | D40220P | 2 | | | | D41254P | 3 | | | 001-099 |
| 0002R | 20 | | QA | | 4-0 | 26-15-11 | GD00339 | DC.. | E | | | D40318J | 2 | | | 115-199 |
| 0003R | 22 | | QA | | 124-4 | 26-15-11 | D40220P | 3 | | | | D41254P | 2 | | | 001-099 |
| 0003R | 20 | | QA | | 154-0 | 26-15-11 | D40220P | 22 | | | | D40318J | 6 | | | 115-199 |
| 0007 | 20 | | GA | | 92-11 | 26-21-11 | D40220P | 7 | | | | D42150P | 1 | | | 001-099 |
| 0007 | 20 | | GA | | 94-0 | 26-21-11 | D40220P | 7 | | | | D42150P | 1 | | | 115-199 |
| 0008 | 20 | | GA | | 2-2 | 26-21-11 | D42150P | 2 | | | | GD01791 | DC.. | E | | 001-099 |
| 0008 | 20 | | GA | | 2-0 | 26-21-11 | D42150P | 2 | | | | GD01791 | DC.. | E | | 115-199 |
| 0009 | 20 | | GA | | 2-3 | 26-21-11 | D42150P | 3 | | | | GD01790 | ST.. | E | | 001-099 |
| 0009 | 20 | | GA | | 2-0 | 26-21-11 | D42150P | 3 | | | | GD01790 | ST.. | E | | 115-199 |
| 0010 | 20 | | GA | | 92-11 | 26-21-11 | D40220P | 8 | | | | D42150P | 4 | | | 001-099 |
| 0010 | 20 | | GA | | 94-0 | 26-21-11 | D40220P | 8 | | | | D42150P | 4 | | | 115-199 |
| 0011 | 20 | | GA | | 2-2 | 26-21-11 | D42150P | 5 | | | | GD01791 | DC.. | E | | 001-099 |
| 0011 | 20 | | GA | | 2-0 | 26-21-11 | D42150P | 5 | | | | GD01791 | DC.. | E | | 115-199 |
| 0012 | 20 | | GA | | 2-3 | 26-21-11 | D42150P | 6 | | | | GD01790 | ST.. | E | | 001-099 |
| 0012 | 20 | | GA | | 2-0 | 26-21-11 | D42150P | 6 | | | | GD01790 | ST.. | E | | 115-199 |
| 0013 | 20 | | GA | | 3-0 | 26-21-11 | D02270 | 3 | | | | GD01791 | DC.. | E | | ALL |
| 0014 | 20 | | GA | | 92-11 | 26-21-11 | D40220P | 9 | | | | D42150P | 8 | | | 001-099 |
| 0014 | 20 | | GA | | 94-0 | 26-21-11 | D40220P | 9 | | | | D42150P | 8 | | | 115-199 |
| 0015 | 22 | | GA | | 46-6 | 26-16-11 | D41264J | 4 | | | | D40220P | 10 | | | 001-099 |
| 0015 | 22 | | GA | | 48-0 | 26-16-11 | D04402 | 4 | | | | D40220P | 10 | | | 115-199 |
| 0016 | 22 | | GA | | 46-6 | 26-16-11 | D41264J | 12 | | | | D40220P | 11 | | | 001-099 |
| 0016 | 22 | | GA | | 48-0 | 26-16-11 | D04402 | 12 | | | | D40220P | 11 | | | 115-199 |
| 0017 | 22 | | GA | | 46-6 | 26-16-11 | D41264J | 11 | | | | D40220P | 12 | | | 001-099 |
| 0017 | 22 | | GA | | 48-0 | 26-16-11 | D04402 | 11 | | | | D40220P | 12 | | | 115-199 |
| 0018 | 22 | | GA | | 3-11 | 26-16-11 | D41264J | 5 | | | | GD02245 | DC.. | E | | 001-099 |
| 0018 | 22 | | GA | | 5-0 | 26-16-11 | D04402 | 5 | | | | GD02245 | DC.. | E | | 115-199 |
| 0019 | 22 | | GA | | 3-11 | 26-16-11 | D41264J | 9 | | | | GD02245 | DC.. | E | | 001-099 |
| 0019 | 22 | | GA | | 5-0 | 26-16-11 | D04402 | 9 | | | | GD02245 | DC.. | E | | 115-199 |
| 0020 | 22 | | GA | | 47-8 | 26-16-11 | D04404 | 4 | | | | D40220P | 13 | | | 001-099 |
| 0020 | 22 | | GA | | 48-0 | 26-16-11 | D04404 | 4 | | | | D40220P | 13 | | | 115-199 |
| 0021 | 22 | | GA | | 47-8 | 26-16-11 | D04404 | 12 | | | | D40220P | 14 | | | 001-099 |
| 0021 | 22 | | GA | | 48-0 | 26-16-11 | D04404 | 12 | | | | D40220P | 14 | | | 115-199 |
| 0022 | 22 | | GA | | 47-8 | 26-16-11 | D04404 | 11 | | | | D40220P | 15 | | | 001-099 |
| 0022 | 22 | | GA | | 48-0 | 26-16-11 | D04404 | 11 | | | | D40220P | 15 | | | 115-199 |
| 0023 | 22 | | GA | | 5-2 | 26-16-11 | D04404 | 5 | | | | GD02245 | DC.. | E | | 001-099 |
| 0023 | 22 | | GA | | 7-0 | 26-16-11 | D04404 | 5 | | | | GD02245 | DC.. | E | | 115-199 |
| 0024 | 22 | | GA | | 5-2 | 26-16-11 | D04404 | 9 | | | | GD02245 | DC.. | E | | 001-099 |
| 0024 | 22 | | GA | | 7-0 | 26-16-11 | D04404 | 9 | | | | GD02245 | DC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2620

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|--------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2628 | 286N2628 | | | P54 TO SEC. 46- E6 RELAY PNL, R. FIRE EXT. BOTTLE AND APU FIREWALL (continued) | | | | | | | | | | | |
| 0033 | 20 | | GA | | 4-4 | 26-23-11 | D04416 | 1 | | | GD02249 | ST.. | E | | 001-099 |
| 0033 | 20 | | GA | | 4-0 | 26-23-11 | D04416 | 1 | | | GD02249 | ST.. | E | | 115-199 |
| 0034 | 20 | | GA | | 100-10 | 26-23-11 | D40220P | 19 | | | D42146P | 8 | | | 001-099 |
| 0034 | 20 | | GA | | 4-0 | 26-23-11 | SM00001 | | 9 | | D42146P | 8 | | | 115-199 |
| 0035 | 20 | | GA | | 4-3 | 26-23-11 | D04416 | 3 | | | GD02293 | DC.. | E | | 001-099 |
| 0035 | 20 | | GA | | 4-0 | 26-23-11 | D04416 | 3 | | | GD02293 | DC.. | E | | 115-199 |
| 0036 | 20 | | GA | | 1-9 | 26-23-11 | D42146P | | | FA | GD02291 | ST.. | E | | 001-099 |
| 0036 | 20 | | GA | | 2-0 | 26-23-11 | D42146P | | | FA | GD02291 | ST.. | E | | 115-199 |
| 0037 | 20 | | GA | | 1-9 | 26-23-11 | D42146P | 3 | | | GD02291 | ST.. | E | | 001-099 |
| 0037 | 20 | | GA | | 2-0 | 26-23-11 | D42146P | 3 | | | GD02291 | ST.. | E | | 115-199 |
| 0038 | 20 | | GA | | 1-9 | 26-23-11 | D42146P | 2 | | | GD02292 | DC.. | E | | 001-099 |
| 0038 | 20 | | GA | | 2-0 | 26-23-11 | D42146P | 2 | | | GD02292 | DC.. | E | | 115-199 |
| 0039 | 20 | | GA | | 100-10 | 26-23-11 | D40220P | 21 | | | D42146P | 4 | | | 001-099 |
| 0039 | 20 | | GA | | 102-0 | 26-23-11 | D40220P | 21 | | | D42146P | 4 | | | 115-199 |
| 0040 | 20 | | GA | | 1-9 | 26-23-11 | D42146P | 6 | | | GD02291 | ST.. | E | | 001-099 |
| 0040 | 20 | | GA | | 2-0 | 26-23-11 | D42146P | 6 | | | GD02291 | ST.. | E | | 115-199 |
| 0041 | 20 | | GA | | 1-9 | 26-23-11 | D42146P | 5 | | | GD02292 | DC.. | E | | 001-099 |
| 0041 | 20 | | GA | | 2-0 | 26-23-11 | D42146P | 5 | | | GD02292 | DC.. | E | | 115-199 |
| 0042 | 20 | | GA | | 82-3 | 28-22-21 | D40942P | 2 | | | D40220P | 16 | | | 001-099 |
| 0042 | 20 | | GA | | 83-0 | 28-22-21 | D40942J | 2 | | | D40220P | 16 | | | 115-199 |
| 0043 | 20 | | GA | | 82-3 | 28-22-21 | D40942P | 3 | | | D40220P | 18 | | | 001-099 |
| 0043 | 20 | | GA | | 83-0 | 28-22-21 | D40942J | 3 | | | D40220P | 18 | | | 115-199 |
| 0044 | 20 | | GA | | 82-3 | 28-22-21 | D40942P | 1 | | | D40220P | 23 | | | 001-099 |
| 0044 | 20 | | GA | | 83-0 | 28-22-21 | D40942J | 1 | | | D40220P | 23 | | | 115-199 |
| 0045 | 20 | | GA | | 3-1 | 26-21-11 | D02270 | 4 | | | GD01790 | ST.. | E | | 001-099 |
| 0045 | 20 | | GA | | 3-0 | 26-21-11 | D02270 | 4 | | | GD01790 | ST.. | E | | 115-199 |
| 0052 | 20 | | GA | | 4-0 | 26-23-11 | D06450 | 2 | | | SM00001 | | 9 | | 115-199 |
| 0053 | 20 | | GA | | 8-0 | 26-23-11 | D06450 | 3 | | | GD03425 | DC.. | E | | 115-199 |
| 0054 | 20 | | GA | | 100-0 | 26-23-11 | D40220P | 19 | | | SM00001 | | 9 | | 115-199 |
| 0057 | 20 | | GA | | 3-5 | 26-21-11 | D42150P | 7 | | | D02270 | 1 | | | 001-099 |
| 0057 | 20 | | GA | | 4-0 | 26-21-11 | D42150P | 7 | | | D02270 | 1 | | | 115-199 |
| 0058R | 20 | | QA | | 124-4 | SPARE | D40220P | 5 | | | D41254P | 4 | | | 001-099 |
| 0066 | 20 | | GA | | 4-2 | 26-23-11 | D42146P | 7 | | | D04416 | 2 | | | 001-099 |
| 0066 | 20 | | GA | | 5-0 | 26-23-11 | D42146P | 7 | | | D04416 | 2 | | | 115-199 |
| 1001 | 20 | | GT | AA | 100-10 | 26-23-11 | D42146P | 1 | | | D40220P | 20 | | | 001-099 |
| 1001 | 20 | | GT | AA | 102-0 | 26-23-11 | D42146P | 1 | | | D40220P | 20 | | | 115-199 |
| 1001Z | | | | AA | 0-0 | 26-23-11 | D42146P | | | FA | D40220P | DED | | | ALL |
| YAAA | | | | | 0-0 | 28-22-21 | D40942P | S/R | | | GD02741 | ST.. | E | | 001-099 |
| YAAA | | | | | 0-0 | 28-22-21 | D40942J | S/R | | | GD02741 | ST.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2620

Page 6 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|-------|----------|---------|------|--------|-------|------|------|---------|------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2631 | 286N2631 | | | | E3-1 TO AFT BODY DISCONNECT - CHANNEL LB | | | | | | | | | | | | |
| 0001 | 22 | | GA | | 125-0 | | 27-21-12 | D41795P | | | | 8 | | D40475J | 8 | | ALL |
| 0002 | 18 | | GA | | 125-0 | | 22-21-11 | D41795P | | | | 21 | | D40475J | 21 | | ALL |
| 0003Y | 22 | | QB | | 125-0 | | 27-41-11 | D41795P | | | | 22 | | D40957P | 1 | | 001-099 |
| 0003Y | 22 | | QB | | 126-0 | | 27-41-11 | D41795P | | | | 22 | | D40957P | 1 | | 115-199 |
| 0004Y | 22 | | QB | | 125-0 | | 27-41-11 | D41795P | | | | 23 | | D40957P | 2 | | 001-099 |
| 0004Y | 22 | | QB | | 126-0 | | 27-41-11 | D41795P | | | | 23 | | D40957P | 2 | | 115-199 |
| 0005Y | 22 | | QB | | 125-0 | | 27-41-11 | D41795P | | | | 24 | | D40957P | 3 | | 001-099 |
| 0005Y | 22 | | QB | | 126-0 | | 27-41-11 | D41795P | | | | 24 | | D40957P | 3 | | 115-199 |
| 0006Y | 22 | | QB | | 125-0 | | 27-41-11 | D41795P | | | | 31 | | D40957P | 4 | | 001-099 |
| 0006Y | 22 | | QB | | 126-0 | | 27-41-11 | D41795P | | | | 31 | | D40957P | 4 | | 115-199 |
| 0007 | 22 | | GA | | 125-0 | | 27-41-11 | D41795P | | | | 32 | | D40957P | 6 | | 001-099 |
| 0007 | 22 | | GA | | 126-0 | | 27-41-11 | D41795P | | | | 32 | | D40957P | 6 | | 115-199 |
| 2001B | 22 | | GB | AD | 125-0 | | 27-21-12 | D41795P | | | | 2 | | D40475J | 2 | | ALL |
| 2001R | 22 | | GB | AD | 0-0 | | 27-21-12 | D41795P | | | | 1 | | D40475J | 1 | | ALL |
| 2002B | 22 | | GB | AF | 125-0 | | 27-21-12 | D41795P | | | | 7 | | D40475J | 7 | | ALL |
| 2002R | 22 | | GB | AF | 0-0 | | 27-21-12 | D41795P | | | | 6 | | D40475J | 6 | | ALL |
| 2003B | 22 | | GB | AA | 125-0 | | 22-21-11 | D41795P | | | | 11 | | D40475J | 11 | | ALL |
| 2003R | 22 | | GB | AA | 0-0 | | 22-21-11 | D41795P | | | | 10 | | D40475J | 10 | | ALL |
| 2004B | 22 | | GB | AC | 125-0 | | 22-21-11 | D41795P | | | | 16 | | D40475J | 16 | | ALL |
| 2004R | 22 | | GB | AC | 0-0 | | 22-21-11 | D41795P | | | | 15 | | D40475J | 15 | | ALL |
| 2005B | 22 | | GB | AG | 125-0 | | 27-21-12 | D41795P | | | | 26 | | D40475J | 18 | | ALL |
| 2005R | 22 | | GB | AG | 0-0 | | 27-21-12 | D41795P | | | | 25 | | D40475J | 17 | | ALL |
| 2006B | 22 | | GB | AH | 125-0 | | 27-21-12 | D41795P | | | | 28 | | D40475J | 20 | | ALL |
| 2006R | 22 | | GB | AH | 0-0 | | 27-21-12 | D41795P | | | | 27 | | D40475J | 19 | | ALL |
| 2007B | 22 | | GB | AJ | 125-0 | | 22-21-11 | D41795P | | | | 30 | | D40475J | 25 | | ALL |
| 2007R | 22 | | GB | AJ | 0-0 | | 22-21-11 | D41795P | | | | 29 | | D40475J | 24 | | ALL |
| 3001B | 22 | | GC | AE | 125-0 | | 27-21-12 | D41795P | | | | 4 | | D40475J | 4 | | ALL |
| 3001R | 22 | | GC | AE | 0-0 | | 27-21-12 | D41795P | | | | 3 | | D40475J | 3 | | ALL |
| 3001Y | 22 | | GC | AE | 0-0 | | 27-21-12 | D41795P | | | | 5 | | D40475J | 5 | | ALL |
| 3002B | 22 | | GC | AB | 125-0 | | 22-21-11 | D41795P | | | | 13 | | D40475J | 13 | | ALL |
| 3002R | 22 | | GC | AB | 0-0 | | 22-21-11 | D41795P | | | | 12 | | D40475J | 12 | | ALL |
| 3002Y | 22 | | GC | AB | 0-0 | | 22-21-11 | D41795P | | | | 14 | | D40475J | 14 | | ALL |
| W2632 | 286N2632 | | | | E/E BAY TO AFT CARGO BAY | | | | | | | | | | | | |
| 0010 | 22 | | GA | | 40-10 | | 52-35-11 | D42038P | | | | 3 | | D40176P | 50 | | 001-099 |
| 0011 | 22 | | GA | | 40-10 | | 52-35-11 | D42038P | | | | 4 | | D40176P | 51 | | 001-099 |
| 0020 | 20 | | GA | | 6-1 | | 38-14-11 | D00052 | | | | 4 | | GD00729 | DC.. | E | 001-099 |
| 0020 | 20 | | GA | | 6-0 | | 38-14-11 | D00052 | | | | 4 | | GD00729 | DC.. | E | 115-199 |
| 0021 | 20 | | GA | | 5-5 | | 38-14-11 | D00052 | | | | 5 | | GD00730 | ST.. | E | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2630

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|-------|-----|--------------------------------------|----------|---------|-------|------|------|--------|-------------|-------|------|------|---------|
| Wire No. | GA | CO TY | Fam | | FT-IN | Diagram | Equip | Term | Type | Splice | | Equip | Term | Type | Splice |
| W2632 | 286N2632 | | | E/E BAY TO AFT CARGO BAY (continued) | | | | | | | | | | | |
| 0021 | 20 | GA | | 6-0 | 38-14-11 | D00052 | | 5 | | | GD00730 | ST.. | E | | 115-199 |
| 0022 | 22 | GA | | 58-0 | 38-14-11 | D00052 | | 3 | | | D40176P | 1 | | | 001-099 |
| 0022 | 22 | GA | | 61-0 | 38-14-11 | D00052 | | 3 | | | D40176P | 1 | | | 115-199 |
| 0023 | 22 | GA | | 24-7 | 38-14-11 | D00052 | | 1 | | | SM00007 | | 9 | | 001-099 |
| 0023 | 22 | GA | | 61-0 | 38-14-11 | D00052 | | 1 | | | D40176P | 2 | | | 115-199 |
| 0024 | 22 | GA | | 24-7 | 38-14-11 | D00052 | | 2 | | | SM00008 | | 9 | | 001-099 |
| 0024 | 22 | GA | | 61-0 | 38-14-11 | D00052 | | 2 | | | D40176P | 3 | | | 115-199 |
| 0025 | 18 | GA | | 54-3 | 38-15-11 | D00062 | | 1 | 18 | | D40178P | 9 | | | 001-099 |
| 0025 | 18 | GA | | 59-0 | 38-15-11 | D00062 | | 1 | 18 | | D40178P | 9 | | | 115-199 |
| 0026 | 18 | GA | | 54-3 | 38-15-11 | D00062 | | 2 | 18 | | D40178P | 10 | | | 001-099 |
| 0026 | 18 | GA | | 59-0 | 38-15-11 | D00062 | | 2 | 18 | | D40178P | 10 | | | 115-199 |
| 0027 | 18 | GA | | 54-3 | 38-15-11 | D00062 | | 3 | 18 | | D40178P | 11 | | | 001-099 |
| 0027 | 18 | GA | | 59-0 | 38-15-11 | D00062 | | 3 | 18 | | D40178P | 11 | | | 115-199 |
| 0028 | 18 | GA | | 1-9 | 38-15-11 | D00062 | | 5 | 18 | | GD03342 | ST.. | E | | 001-099 |
| 0028 | 18 | GA | | 2-0 | 38-15-11 | D00062 | | 5 | 18 | | GD03342 | ST.. | E | | 115-199 |
| 0030 | 16 | GA | | 40-10 | 52-35-11 | D40178P | | 8 | | | D42038P | 20 | | | 001-099 |
| 0030 | 16 | GA | | 57-0 | 52-35-11 | D40178P | | 8 | | | D42038P | 20 | | | 115-199 |
| 0031 | 16 | GA | | 40-10 | 52-35-11 | D40178P | | 6 | | | D42038P | 22 | | | 001-099 |
| 0031 | 16 | GA | | 57-0 | 52-35-11 | D40178P | | 6 | | | D42038P | 22 | | | 115-199 |
| 0032 | 16 | GA | | 40-10 | 52-35-11 | D40178P | | 7 | | | D42038P | 24 | | | 001-099 |
| 0032 | 16 | GA | | 57-0 | 52-35-11 | D40178P | | 7 | | | D42038P | 24 | | | 115-199 |
| 0044 | 20 | GA | | 22-9 | 38-14-11 | SM00008 | | | 9 | | D00056 | 2 | | | 001-099 |
| 0044 | 20 | GA | | 61-0 | 38-14-11 | D40176P | | 4 | | | D00056 | 2 | | | 115-199 |
| 0045 | 20 | GA | | 22-9 | 38-14-11 | SM00007 | | | 9 | | D00056 | 1 | | | 001-099 |
| 0045 | 20 | GA | | 61-0 | 38-14-11 | D40176P | | 5 | | | D00056 | 1 | | | 115-199 |
| 0048 | 20 | GA | | 15-0 | 30-71-21 | SM00006 | | | 9 | | SP00362 | | 9 | | 115-199 |
| 0050 | 20 | GA | | 60-3 | 30-71-11 | D40176P | | 15 | | | SP00366 | | 9 | | 001-099 |
| 0050 | 20 | GA | | 68-0 | 30-71-11 | D40176P | | 15 | | | SP00366 | | 9 | | 115-199 |
| 0051 | 18 | GA | | 59-8 | 38-15-11 | D00064 | | 2 | 18 | | D40178P | 12 | | | 001-099 |
| 0051 | 18 | GA | | 62-0 | 38-15-11 | D00064 | | 2 | 18 | | D40178P | 12 | | | 115-199 |
| 0052 | 18 | GA | | 3-4 | 38-15-11 | D00064 | | 3 | 18 | | GD02388 | AC.. | E | | 001-099 |
| 0052 | 18 | GA | | 11-0 | 38-15-11 | D00064 | | 3 | 18 | | GD02388 | AC.. | E | | 115-199 |
| 0053 | 20 | GA | | 2-3 | 21-31-21 | D02336 | | 2 | | | GD00717 | ST.. | E | | 001-099 |
| 0053 | 20 | GA | | 3-0 | 21-31-21 | D02336 | | 2 | | | GD00717 | ST.. | E | | 115-199 |
| 0054 | 20 | GA | | 63-3 | 21-31-21 | D02336 | | 6 | | | D40176P | 27 | | | 001-099 |
| 0054 | 20 | GA | | 68-0 | 21-31-21 | D02336 | | 6 | | | D40176P | 27 | | | 115-199 |
| 0057 | 20 | GA | | 2-10 | 21-58-21 | D02358 | | 5 | | | GD03280 | AC.. | E | | 001-099 |
| 0057 | 20 | GA | | 3-0 | 21-58-21 | D02358 | | 5 | | | GD03280 | AC.. | E | | 115-199 |
| 0058 | 20 | GA | | 59-1 | 21-58-21 | D02358 | | 6 | | | D40176P | 25 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2630

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W2632 | 286N2632 | | | | E/E BAY TO AFT CARGO BAY (continued) | | | | | | | | | | | |
| 0058 | 20 | | GA | | 64-0 | 21-58-21 | D02358 | | | | | D40176P | 25 | | | 115-199 |
| 0059 | 18 | | GA | | 59-1 | 21-58-21 | D02358 | | | | | D40178P | 15 | | | 001-099 |
| 0059 | 18 | | GA | | 64-0 | 21-58-21 | D02358 | | | | | D40178P | 15 | | | 115-199 |
| 0060 | 18 | | GA | | 59-1 | 21-58-21 | D02358 | | | | | D40178P | 14 | | | 001-099 |
| 0060 | 18 | | GA | | 64-0 | 21-58-21 | D02358 | | | | | D40178P | 14 | | | 115-199 |
| 0061 | 18 | | GA | | 59-1 | 21-58-21 | D02358 | | | | | D40178P | 13 | | | 001-099 |
| 0061 | 18 | | GA | | 64-0 | 21-58-21 | D02358 | | | | | D40178P | 13 | | | 115-199 |
| 0062 | 16 | | GA | | 3-6 | 21-58-21 | D02358 | | | | | GD00720 | ST.. | E | | 001-099 |
| 0062 | 16 | | GA | | 4-0 | 21-58-21 | D02358 | | | | | GD00720 | ST.. | E | | 115-199 |
| 0063 | 20 | | GA | | 75-5 | 30-71-21 | D40176P | | | | | SP00478 | | 9 | | 001-099 |
| 0063 | 20 | | GA | | 35-0 | 30-71-21 | D40176P | | | | | SM00006 | | 9 | | 115-199 |
| 0064 | 20 | | GA | | 36-0 | 30-71-21 | SM00006 | | | 9 | | SP00478 | | 9 | | 115-199 |
| 0065 | 20 | | GA | | 2-3 | 21-31-21 | D02336 | | | | | GD00718 | AC.. | E | | 001-099 |
| 0065 | 20 | | GA | | 3-0 | 21-31-21 | D02336 | | | | | GD00718 | AC.. | E | | 115-199 |
| 0066 | 18 | | GA | | 39-9 | 33-37-21 | D40178P | | | | | SP00388 | | 9 | | 001-099 |
| 0066 | 18 | | GA | | 42-0 | 33-37-21 | D40178P | | | | | SP00388 | | 9 | | 115-199 |
| 0070 | 20 | | GA | | 14-10 | 33-37-21 | D42038P | | | | | SP00386 | | 9 | | 001-099 |
| 0071 | 22 | | GA | | 7-10 | 33-37-21 | D42038P | | | | | SM00009 | | 9 | | 001-099 |
| 0072 | 20 | | GA | | 57-0 | 25-51-21 | D40176P | | | | | D42038P | 10 | | | 115-199 |
| 0073 | 20 | | GA | | 40-10 | SPARE | D40176P | | | | | D42038P | 17 | | | 001-099 |
| 0073 | 18 | | GA | | 57-0 | 25-51-21 | D40178P | | | | | D42038P | 14 | | | 115-199 |
| 0074 | 18 | | GA | | 57-0 | 25-51-21 | D40178P | | | | | D42038P | 16 | | | 115-199 |
| 0075 | 18 | | GA | | 57-0 | 25-51-21 | D40178P | | | | | D42038P | 18 | | | 115-199 |
| 0076 | 20 | | GA | | 9-0 | 25-51-21 | D42038P | | | | | GD02850 | DC.. | E | | 115-199 |
| 0077 | 20 | | GA | | 9-0 | 25-51-21 | D42038P | | | | | GD02850 | DC.. | E | | 115-199 |
| 0078 | 20 | | GA | | 14-0 | 33-37-21 | D42038P | | | | | S10311 | 3 | C | | 115-199 |
| 0080 | 20 | | GA | | 29-0 | 33-37-21 | D42038P | | | | | SP00386 | | 9 | | 115-199 |
| 0081 | 22 | | GA | | 29-0 | 33-37-21 | D42038P | | | | | SP01054 | | 9 | | 115-199 |
| 0082 | 20 | | GA | | 23-0 | 33-37-21 | S10311 | | | C | | SP00388 | | 9 | | 115-199 |
| 0096 | 20 | | GA | | 2-3 | 21-31-21 | D02336 | | | | | GD00718 | AC.. | E | | 001-099 |
| 0096 | 20 | | GA | | 3-0 | 21-31-21 | D02336 | | | | | GD00718 | AC.. | E | | 115-199 |
| 0101 | 20 | | GA | | 54-1 | 30-71-21 | D40176P | | | | | SP01902 | | 9 | | 001-099 |
| 0101 | 20 | | GA | | 61-0 | 30-71-21 | D40176P | | | | | SP00408 | | 9 | | 115-199 |
| 0109 | 20 | | GA | | 16-0 | 30-71-21 | SP00364 | | | 9 | | SP00410 | | 9 | | 115-199 |
| 0110 | 22 | | GA | | 34-0 | 38-14-11 | D40176P | | | | | SM00007 | | 9 | | 001-099 |
| 0111 | 22 | | GA | | 34-0 | 38-14-11 | D40176P | | | | | SM00008 | | 9 | | 001-099 |
| 0127 | 20 | | GA | | 9-4 | 30-71-21 | SP01896 | | | 9 | | SP01898 | | 9 | | 001-099 |
| 0128 | 20 | | GA | | 12-7 | 30-71-21 | SP01896 | | | 9 | | SP01900 | | 9 | | 001-099 |
| 0227 | 22 | | GA | | 34-0 | 52-35-11 | D40176P | | | 19 | | SM00009 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2630

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2632 | 286N2632 | | | E/E BAY TO AFT CARGO BAY (continued) | | | | | | | | | | | |
| 0228 | 22 | | GA | | 0-7 | 52-35-11 | S10181 | 2 | C | * | S10181 | 5 | C | | 001-099 |
| 0229 | 22 | | GA | | 12-4 | 52-35-11 | SM00009 | | 9 | | S10181 | 2 | C | * | 001-099 |
| 0230 | 22 | | GA | | 15-8 | 52-35-11 | S10181 | 1 | C | | SP00184 | | 9 | | 001-099 |
| 0231 | 22 | | GA | | 15-8 | 52-35-11 | S10181 | 6 | C | | SP00186 | | 9 | | 001-099 |
| 0250 | 22 | | GA | | 58-0 | 21-58-24 | D40176P | 46 | | | D04216 | 3 | | | 115-199 |
| 0251 | 22 | | GA | | 58-0 | 21-58-24 | D40176P | 45 | | | D04216 | 2 | | | 115-199 |
| 0252 | 22 | | GA | | 58-0 | 21-58-24 | D40176P | 44 | | | D04216 | 1 | | | 115-199 |
| 0253 | 22 | | GA | | 58-0 | 21-58-24 | D40176P | 48 | | | D04216 | 5 | | | 115-199 |
| 0254 | 22 | | GA | | 58-0 | 21-58-24 | D40176P | 47 | | | D04216 | 6 | | | 115-199 |
| 0255 | 20 | | GA | | 5-0 | 21-58-24 | GD02610 | ST.. | 2 | | D04216 | 7 | | | 115-199 |
| 2001B | 24 | | GL | AA | 44-6 | 52-35-11 | D40176P | 18 | | | SP00054 | | 9 | | 001-099 |
| 2001B | 24 | | GL | AA | 46-0 | 52-35-11 | D40176P | 18 | | | SP00054 | | 9 | | 115-199 |
| 2001R | 24 | | GL | AA | 0-0 | 52-35-11 | D40176P | 17 | | | SP00048 | | 9 | | ALL |
| 2002B | 24 | | GL | AB | 49-0 | 52-71-21 | D40176P | 20 | | | SP01134 | | 9 | | 115-199 |
| 2002R | 24 | | GL | AB | 0-0 | 52-71-21 | D40176P | 19 | | | SP01132 | | 9 | | 115-199 |
| 2003B | 24 | | GL | AC | 48-5 | 52-35-11 | D40176P | 22 | | | SP00102 | | 9 | | 001-099 |
| 2003B | 24 | | GL | AC | 48-0 | 52-35-11 | D40176P | 22 | | | SP00102 | | 9 | | 115-199 |
| 2003R | 24 | | GL | AC | 0-0 | 52-35-11 | D40176P | 21 | | | SP00100 | | 9 | | ALL |
| 2005B | 24 | | GL | AL | 43-7 | 52-71-21 | D40176P | 31 | | | SP00174 | | 9 | | 001-099 |
| 2005B | 24 | | GL | AL | 43-0 | 52-71-21 | D40176P | 31 | | | SP00174 | | 9 | | 115-199 |
| 2005R | 24 | | GL | AL | 0-0 | 52-71-21 | D40176P | 30 | | | SP00176 | | 9 | | ALL |
| 2008B | 20 | | GB | AN | 63-3 | 21-31-21 | D40176P | 10 | | | D02336 | 5 | | | 001-099 |
| 2008B | 20 | | GB | AN | 68-0 | 21-31-21 | D40176P | 10 | | | D02336 | 5 | | | 115-199 |
| 2008R | 20 | | GB | AN | 0-0 | 21-31-21 | D40176P | 9 | | | D02336 | 1 | | | ALL |
| 2009B | 24 | | GL | AP | 64-6 | 21-31-21 | D40176P | 29 | | | SP01536 | | 9 | | 001-099 |
| 2009B | 24 | | GL | AP | 68-0 | 21-31-21 | D40176P | 29 | | | SP01536 | | 9 | | 115-199 |
| 2009R | 24 | | GL | AP | 0-0 | 21-31-21 | D40176P | 28 | | | SP01534 | | 9 | | ALL |
| 2501B | 24 | | G2 | AR | 63-3 | 21-31-21 | D02336 | 10 | | | D40176P | 7 | | | 001-099 |
| 2501B | 24 | | G2 | AR | 68-0 | 21-31-21 | D02336 | 10 | | | D40176P | 7 | | | 115-199 |
| 2501R | 24 | | G2 | AR | 0-0 | 21-31-21 | D02336 | 9 | | | D40176P | 6 | | | ALL |
| 2501Z | | | | AR | 0-0 | 21-31-21 | GD00717 | ST.. | E | | D40176P | 8 | | | ALL |
| A-BE | | | | | 0-0 | 30-71-21 | B10223 | =1 | | | SP01902 | | 9 | | 001-099 |
| A-BF | | | | | 0-0 | 30-71-21 | B10223 | =2 | | | SP01896 | | 9 | | 001-099 |
| A-BG | | | | | 0-0 | 30-71-21 | B10217 | =1 | | | SP01900 | | 9 | | 001-099 |
| A-BH | | | | | 0-0 | 30-71-21 | B10217 | =2 | | | GD03105 | AC.. | E | | 001-099 |
| A-BI | | | | | 0-0 | 30-71-21 | B10220 | =1 | | | SP01898 | | 9 | | 001-099 |
| A-BL | | | | | 0-0 | 52-35-11 | SP00054 | | 9 | | S10357 | BLU | | | ALL |
| A-BM | | | | | 0-0 | 30-71-21 | B10220 | =2 | | | GD02370 | AC.. | E | | 001-099 |
| A-BO | | | | | 0-0 | 30-71-21 | B10221 | =1 | | | SP01898 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2630

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | |
|------------|-------------|----|----|--------------------------------------|---------|----------|---------|-------|------|------|--------|---------|------|-------------|---------|
| | GA | CO | TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type |
| Wire No. | | | | | | | | | | | | | | | |
| W2632 | 286N2632 | | | E/E BAY TO AFT CARGO BAY (continued) | | | | | | | | | | | |
| A-BP | | | | | 0-0 | 30-71-21 | B10221 | | =2 | | | GD02370 | AC.. | E | 001-099 |
| A-BQ | | | | | 0-0 | 30-71-21 | B10219 | | =1 | | | SP01898 | | 9 | 001-099 |
| A-BR | | | | | 0-0 | 30-71-21 | B10219 | | =2 | | | GD02370 | AC.. | E | 001-099 |
| A-BS | | | | | 0-0 | 30-71-21 | B10222 | | =1 | | | SP01896 | | 9 | 001-099 |
| A-BT | | | | | 0-0 | 30-71-21 | B10222 | | =2 | | | GD00726 | AC.. | E | 001-099 |
| A-BU | | | | | 0-0 | 30-71-21 | B10201 | | =1 | | | SP01900 | CAP | Y | 001-099 |
| A-BW | | | | | 0-0 | 30-71-21 | B10201 | | =2 | | | GD03105 | CAP | Y | 001-099 |
| A-RD | | | | | 0-0 | 52-35-11 | SP00048 | | | 9 | | S10357 | RED | | ALL |
| B-GD | | | | | 0-0 | 30-71-21 | B00092 | | =2 | | | GD02747 | AC.. | E | ALL |
| B-PR | | | | | 0-0 | 30-71-21 | SP00478 | | | 9 | | B00092 | | =1 | ALL |
| C-BL | | | | | 0-0 | 52-35-11 | SP00102 | | | 9 | | S10359 | BLU | | ALL |
| C-RD | | | | | 0-0 | 52-35-11 | SP00100 | | | 9 | | S10359 | RED | | ALL |
| D-BK | | | | | 0-0 | 30-71-21 | SP00362 | | | 9 | | B00114 | BLK | | 115-199 |
| D-WT | | | | | 0-0 | 30-71-21 | B00114 | WHT | | | | GD00724 | AC.. | E | 115-199 |
| E-BK | | | | | 0-0 | 30-71-21 | SP00364 | | | 9 | | B00116 | BLK | | 115-199 |
| E-WT | | | | | 0-0 | 30-71-21 | B00116 | WHT | | | | GD00726 | AC.. | E | 115-199 |
| G-BL | | | | | 0-0 | 52-71-21 | S10088 | | | | | SP00174 | | 9 | ALL |
| G-RD | | | | | 0-0 | 52-71-21 | S10088 | | | | | SP00176 | | 9 | ALL |
| H-AC | | | | | 0-0 | 30-71-11 | B00042 | | =2 | | | GD01571 | AC.. | E | ALL |
| H-PR | | | | | 0-0 | 30-71-11 | SP00366 | | | 9 | | B00042 | | =1 | ALL |
| H-ST | | | | | 0-0 | 30-71-11 | B00042 | | =3 | | | GD01572 | ST.. | E | ALL |
| J-BL | | | | | 0-0 | 52-71-21 | SP01134 | | | 9 | | S10089 | BLU | | 115-199 |
| J-RD | | | | | 0-0 | 52-71-21 | SP01132 | | | 9 | | S10089 | RED | | 115-199 |
| M-BK | | | | | 0-0 | 30-71-21 | SP00410 | | | 9 | | B00113 | BLK | | 115-199 |
| M-WT | | | | | 0-0 | 30-71-21 | GD02370 | AC.. | E | | | B00113 | WHT | | 115-199 |
| N-BK | | | | | 0-0 | 30-71-21 | SP00410 | | | 9 | | B00111 | BLK | | 115-199 |
| N-WT | | | | | 0-0 | 30-71-21 | GD02370 | AC.. | E | | | B00111 | WHT | | 115-199 |
| O-BK | | | | | 0-0 | 30-71-21 | B00109 | BLK | | | | SP00410 | | 9 | 115-199 |
| O-WT | | | | | 0-0 | 30-71-21 | B00109 | WHT | | | | GD02370 | AC.. | E | 115-199 |
| R-PR | | | | | 0-0 | 30-71-21 | SP00408 | | | 9 | | B10105 | | =1 | 115-199 |
| S-GD | | | | | 0-0 | 30-71-21 | B10105 | | =2 | | | SP00364 | | 9 | 115-199 |
| W-BN | | | | | 0-0 | 30-71-21 | SP00478 | | | 9 | | B10127 | | =1 | 001-099 |
| W-BN | | | | | 0-0 | 30-71-21 | SP00478 | | | 9 | | B10127 | BRN | | 115-199 |
| W-OR | | | | | 0-0 | 30-71-21 | B10127 | | =2 | | | GD02747 | AC.. | E | 001-099 |
| W-OR | | | | | 0-0 | 30-71-21 | B10127 | ORG | | | | GD02747 | AC.. | E | 115-199 |
| X-BN | | | | | 0-0 | 30-71-21 | SP00478 | | | 9 | | B10126 | | =1 | 001-099 |
| X-BN | | | | | 0-0 | 30-71-21 | SP00478 | | | 9 | | B10126 | BRN | | 115-199 |
| X-OR | | | | | 0-0 | 30-71-21 | B10126 | | =2 | | | GD02747 | AC.. | E | 001-099 |
| X-OR | | | | | 0-0 | 30-71-21 | B10126 | ORG | | | | GD02747 | AC.. | E | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2630

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2634 | 286N2634 | | | | STA 1460 TO AFT CARGO BAY - AFT EQUIP COOLING | | | | | | | | | | |
| 0001 | 20 | | GA | | 6-0 | 21-58-21 | D02360 | | 5 | | GD03282 | AC.. | E | | ALL |
| 0002 | 20 | | GA | | 142-0 | 21-58-21 | D02360 | | 6 | | D40206P | 2 | | | ALL |
| 0003 | 18 | | GA | | 142-0 | 21-58-21 | D02360 | | 3 | | D40206P | 14 | | | ALL |
| 0004 | 18 | | GA | | 142-0 | 21-58-21 | D02360 | | 2 | | D40206P | 16 | | | ALL |
| 0005 | 18 | | GA | | 142-0 | 21-58-21 | D02360 | | 1 | | D40206P | 18 | | | ALL |
| 0006 | 16 | | GA | | 5-0 | 21-58-21 | D02360 | | 7 | | GD01424 | ST.. | E | | ALL |
| 0007 | 20 | | GA | | 5-0 | 21-31-11 | D02332 | | 2 | | GD00289 | ST.. | E | | ALL |
| 0008 | 20 | | GA | | 144-0 | 21-31-11 | D02332 | | 6 | | D41924P | 1 | | | ALL |
| 0009 | 20 | | GA | | 5-0 | 21-31-11 | D02332 | | 7 | | GD00291 | AC.. | E | | ALL |
| 0010 | 24 | | GK | | 5-0 | 21-31-11 | D02334 | | 11 | | GD00289 | ST.. | E | | 001-099 |
| 0010 | 24 | | GK | | 4-0 | 21-31-11 | D02334 | | 11 | | GD00289 | ST.. | E | | 115-199 |
| 0011 | 14 | | GA | | 95-0 | 21-44-11 | D41942P | | 14 | | D01640 | 4 | 14 | | ALL |
| 0012 | 14 | | GA | | 95-0 | 21-44-11 | D41942P | | 16 | | D01640 | 7 | 14 | | ALL |
| 0013 | 14 | | GA | | 95-0 | 21-44-11 | D41942P | | 18 | | D01640 | 10 | 14 | | ALL |
| 0014 | 22 | | GA | | 95-0 | 21-44-11 | D01640 | | 2 | | D41942P | 1 | | | ALL |
| 0015 | 22 | | GA | | 95-0 | 21-44-11 | D01640 | | 1 | | D41942P | 2 | | | ALL |
| 0016 | 22 | | GA | | 95-0 | 21-44-11 | D01640 | | 12 | | D41942P | 3 | | | ALL |
| 0017 | 18 | | GA | | 5-0 | 21-44-11 | D01640 | | 11 | 18 | GD01425 | ST.. | E | | ALL |
| 0021 | 20 | | GA | | 13-0 | SPARE | D40206P | | 8 | | D41924P | 11 | | | 115-199 |
| 0022 | 20 | | GA | | 13-0 | SPARE | D40206P | | 9 | | D41924P | 12 | | | 115-199 |
| 0023 | 20 | | GA | | 25-0 | SPARE | D40206P | | 10 | | D41942P | 5 | | | 115-199 |
| 0025 | 20 | | GA | | 26-0 | SPARE | D41942P | | 7 | | D41924P | 13 | | | 115-199 |
| 0026 | 20 | | GA | | 26-0 | SPARE | D41942P | | 8 | | D41924P | 14 | | | 115-199 |
| 0096 | 20 | | GA | | 5-0 | 21-31-11 | D02332 | | 3 | | GD00291 | AC.. | E | | ALL |
| 2001B | 24 | | GL | AC | 143-0 | 21-31-11 | D02334 | | 5 | | D41924P | 9 | | | ALL |
| 2001R | 24 | | GL | AC | 0-0 | 21-31-11 | D02334 | | 6 | | D41924P | 8 | | | ALL |
| 2002B | 20 | | GB | AE | 143-0 | 21-31-11 | D41924P | | 6 | | D02332 | 5 | | | ALL |
| 2002R | 20 | | GB | AE | 0-0 | 21-31-11 | D41924P | | 5 | | D02332 | 1 | | | ALL |
| 2009B | 24 | | GL | AP | 4-0 | 21-31-21 | D02334 | | 8 | | SP01536 | | 9 | | ALL |
| 2009R | 24 | | GL | AP | 0-0 | 21-31-21 | D02334 | | 9 | | SP01534 | | 9 | | ALL |
| 2501B | 24 | | G2 | AA | 143-0 | 21-31-11 | D41924P | | 3 | | D02332 | 10 | | | ALL |
| 2501R | 24 | | G2 | AA | 0-0 | 21-31-11 | D41924P | | 2 | | D02332 | 9 | | | ALL |
| 2501Z | | | | AA | 0-0 | 21-31-11 | D41924P | | 4 | | GD00289 | ST.. | E | | ALL |
| 3002B | 22 | | GC | AD | 139-0 | 21-31-31 | D02334 | | 2 | | D40206P | 7 | | | ALL |
| 3002R | 22 | | GC | AD | 0-0 | 21-31-31 | D02334 | | 3 | | D40206P | 5 | | | ALL |
| 3002Y | 22 | | GC | AD | 0-0 | 21-31-31 | D02334 | | 1 | | D40206P | 6 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2630

Page 6 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|-------------|--------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W2642 | 286N2642 | | | | E5-2 TO LEFT BODY/SPAR INSTALLATION - L2A | | | | | | | | | | | |
| 0001 | 20 | | GA | | 103-0 | SPARE | | D42518P | 7 | | | D40082J | 17 | | | 001-099 |
| 0001 | 20 | | GA | | 93-0 | SPARE | | D41668P | 6 | | | D40082J | 17 | | | 115-199 |
| 0002 | 20 | | GA | | 93-0 | SPARE | | D41668P | 13 | | | D40082J | 18 | | | 115-199 |
| 0003 | 20 | | GA | | 93-0 | SPARE | | D41668P | 12 | | | D40082J | 19 | | | 115-199 |
| 2501B | 20 | | GU | BA | 103-0 | 32-42-11 | | D42518P | 1 | | | D40082J | 9 | | | 001-099 |
| 2501B | 20 | | GU | BA | 93-0 | 32-42-11 | | D41668P | 1 | | | D40082J | 9 | | | 115-199 |
| 2501R | 20 | | GU | BA | 0-0 | 32-42-11 | | D42518P | 2 | | | D40082J | 10 | | | 001-099 |
| 2501R | 20 | | GU | BA | 0-0 | 32-42-11 | | D41668P | 2 | | | D40082J | 10 | | | 115-199 |
| 2501Z | | | | BA | 0-0 | 32-42-11 | | D42518P | 5 | | | D40082J | 7 | | | 001-099 |
| 2501Z | | | | BA | 0-0 | 32-42-11 | | D41668P | 5 | | | D40082J | 7 | | | 115-199 |
| 2502B | 20 | | GU | BB | 103-0 | 32-42-11 | | D42518P | 3 | | | D40082J | 3 | | | 001-099 |
| 2502B | 20 | | GU | BB | 93-0 | 32-42-11 | | D41668P | 3 | | | D40082J | 3 | | | 115-199 |
| 2502R | 20 | | GU | BB | 0-0 | 32-42-11 | | D42518P | 4 | | | D40082J | 4 | | | 001-099 |
| 2502R | 20 | | GU | BB | 0-0 | 32-42-11 | | D41668P | 4 | | | D40082J | 4 | | | 115-199 |
| 2502Z | | | | BB | 0-0 | 32-42-11 | | D42518P | 6 | | | D40082J | 5 | | | 001-099 |
| 2502Z | | | | BB | 0-0 | 32-42-11 | | D41668P | 11 | | | D40082J | 5 | | | 115-199 |
| 2503B | 20 | | GU | BC | 15-0 | 32-09-11 | | D40082J | 12 | | | SP01254 | | 9 | | 001-099 |
| 2503B | 20 | | GF | BC | 13-0 | 32-09-11 | | D40082J | 12 | | | SP01254 | | 9 | | 115-199 |
| 2503R | 20 | | GU | BC | 0-0 | 32-09-11 | | D40082J | 11 | | | SP01256 | | 9 | | 001-099 |
| 2503R | 20 | | GF | BC | 0-0 | 32-09-11 | | D40082J | 11 | | | SP01256 | | 9 | | 115-199 |
| 2503Z | | | | BC | 0-0 | 32-09-11 | | D40082J | DED | | | SP01254 | | 9 | | ALL |
| 4501G | 20 | | XU | TA | 93-0 | 32-46-11 | | D41668P | 7 | | | D40082J | 13 | | | 115-199 |
| 4501W | 20 | | XU | TA | 0-0 | 32-46-11 | | D41668P | 8 | | | D40082J | 14 | | | 115-199 |
| 4502G | 20 | | XU | TB | 93-0 | 32-46-11 | | D41668P | 9 | | | D40082J | 1 | | | 115-199 |
| 4502W | 20 | | XU | TB | 0-0 | 32-46-11 | | D41668P | 10 | | | D40082J | 2 | | | 115-199 |
| YAAB | | | | | 0-0 | 32-09-11 | | D40082J | S/R | | | GD02743 | ST.. | E | | ALL |
| W2644 | 286N2644 | | | | E6-2 TO RIGHT BODY/SPAR INSTALLATION - L2B | | | | | | | | | | | |
| 0001 | 20 | | GA | | 81-0 | 32-42-11 | | D42510P | 10 | | | D41818J | 1 | | | 001-099 |
| 0001 | 20 | | GA | | 93-0 | 32-42-11 | | D41670P | 10 | | | D41818J | 1 | | | 115-199 |
| 0002 | 20 | | GA | | 81-0 | 32-42-12 | | D42510P | 7 | | | D41818J | 2 | | | 001-099 |
| 0002 | 20 | | GA | | 93-0 | 32-42-12 | | D41670P | 11 | | | D41818J | 2 | | | 115-199 |
| 0003 | 20 | | GA | | 81-0 | 32-42-12 | | D42510P | 8 | | | D41818J | 3 | | | 001-099 |
| 0003 | 20 | | GA | | 93-0 | 32-42-12 | | D41670P | 12 | | | D41818J | 3 | | | 115-199 |
| 0004 | 20 | | GA | | 81-0 | 32-42-11 | | D42510P | 11 | | | D41818J | 4 | | | 001-099 |
| 0004 | 20 | | GA | | 93-0 | 32-42-11 | | D41670P | 13 | | | D41818J | 4 | | | 115-199 |
| 0005 | 20 | | GA | | 81-0 | 32-42-11 | | D42510P | 9 | | | D41818J | 5 | | | 001-099 |
| 0005 | 20 | | GA | | 93-0 | 32-42-11 | | D41670P | 14 | | | D41818J | 5 | | | 115-199 |
| 0006 | 20 | | GA | | 81-0 | 32-42-11 | | D42510P | 12 | | | D41818J | 6 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2640

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2644 | 286N2644 | E6-2 TO RIGHT BODY/SPAR INSTALLATION - L2B (continued) | | | | | | | | | | | | | |
| 0006 | 20 | GA | | | 93-0 | 32-42-11 | D41670P | 15 | | | D41818J | 6 | | | 115-199 |
| 0007 | 20 | GA | | | 80-0 | 32-42-11 | D42512P | 2 | | | D43010J | 1 | | | 001-099 |
| 0007 | 20 | GA | | | 93-0 | 32-42-11 | D43012P | 17 | | | D43010J | 1 | | | 115-199 |
| 0008 | 20 | GA | | | 80-0 | 32-42-11 | D42512P | 1 | | | D43010J | 3 | | | 001-099 |
| 0008 | 20 | GA | | | 93-0 | 32-42-11 | D43012P | 16 | | | D43010J | 3 | | | 115-199 |
| 0009 | 20 | GA | | | 87-0 | SPARE | D42510P | 13 | | | D40442J | 17 | | | 001-099 |
| 0009 | 20 | GA | | | 100-0 | SPARE | D41670P | 23 | | | D40442J | 17 | | | 115-199 |
| 0010 | 20 | GA | | | 100-0 | SPARE | D41670P | 21 | | | D40442J | 18 | | | 115-199 |
| 0011 | 20 | GA | | | 100-0 | SPARE | D41670P | 22 | | | D40442J | CAP | Y | | 115-199 |
| 0027 | 20 | GA | | | 81-0 | SPARE | D42510P | 14 | | | D41818J | 7 | | | 001-099 |
| 0028 | 20 | GA | | | 80-0 | SPARE | D42512P | 4 | | | D43010J | 4 | | | 001-099 |
| 0029 | 20 | GA | | | 80-0 | SPARE | D42512P | 5 | | | D43010J | 5 | | | 001-099 |
| 2501B | 20 | GU | BA | | 87-0 | 32-42-11 | D42510P | 1 | | | D40442J | 9 | | | 001-099 |
| 2501B | 20 | GU | BA | | 100-0 | 32-42-11 | D41670P | 1 | | | D40442J | 9 | | | 115-199 |
| 2501R | 20 | GU | BA | | 0-0 | 32-42-11 | D42510P | 2 | | | D40442J | 10 | | | 001-099 |
| 2501R | 20 | GU | BA | | 0-0 | 32-42-11 | D41670P | 2 | | | D40442J | 10 | | | 115-199 |
| 2501Z | | | BA | | 0-0 | 32-42-11 | D42510P | 5 | | | D40442J | 7 | | | 001-099 |
| 2501Z | | | BA | | 0-0 | 32-42-11 | D41670P | 5 | | | D40442J | 7 | | | 115-199 |
| 2502B | 20 | GU | BB | | 87-0 | 32-42-11 | D42510P | 3 | | | D40442J | 3 | | | 001-099 |
| 2502B | 20 | GU | BB | | 100-0 | 32-42-11 | D41670P | 3 | | | D40442J | 3 | | | 115-199 |
| 2502R | 20 | GU | BB | | 0-0 | 32-42-11 | D42510P | 4 | | | D40442J | 4 | | | 001-099 |
| 2502R | 20 | GU | BB | | 0-0 | 32-42-11 | D41670P | 4 | | | D40442J | 4 | | | 115-199 |
| 2502Z | | | BB | | 0-0 | 32-42-11 | D42510P | 6 | | | D40442J | 5 | | | 001-099 |
| 2502Z | | | BB | | 0-0 | 32-42-11 | D41670P | 18 | | | D40442J | 5 | | | 115-199 |
| 2503B | 20 | GU | BC | | 13-0 | 32-09-11 | D40442J | 12 | | | SP01250 | | 9 | | 001-099 |
| 2503B | 20 | GF | BC | | 14-0 | 32-09-11 | D40442J | 12 | | | SP01250 | | 9 | | 115-199 |
| 2503R | 20 | GU | BC | | 0-0 | 32-09-11 | D40442J | 11 | | | SP01252 | | 9 | | 001-099 |
| 2503R | 20 | GF | BC | | 0-0 | 32-09-11 | D40442J | 11 | | | SP01252 | | 9 | | 115-199 |
| 2503Z | | | BC | | 0-0 | 32-09-11 | D40442J | DED | | | SP01250 | | 9 | | ALL |
| 4501G | 20 | XU | TA | | 100-0 | 32-46-11 | D41670P | 6 | | | D40442J | 13 | | | 115-199 |
| 4501W | 20 | XU | TA | | 0-0 | 32-46-11 | D41670P | 7 | | | D40442J | 14 | | | 115-199 |
| 4502G | 20 | XU | TB | | 100-0 | 32-46-11 | D41670P | 8 | | | D40442J | 1 | | | 115-199 |
| 4502W | 20 | XU | TB | | 0-0 | 32-46-11 | D41670P | 9 | | | D40442J | 2 | | | 115-199 |
| YAAD | | | | | 0-0 | 32-09-11 | D40442J | S/R | | | GD02741 | ST.. | E | | ALL |
| W2646 | 286N2646 | E5-2 TO LEFT BODY/SPAR INSTALLATION - R2A | | | | | | | | | | | | | |
| 0001 | 20 | GA | | | 103-0 | 32-42-11 | D42514P | 2 | | | D41812J | 11 | | | 001-099 |
| 0001 | 20 | GA | | | 89-0 | 32-42-11 | D43014P | 17 | | | D41812J | 11 | | | 115-199 |
| 0002 | 20 | GA | | | 104-0 | 32-42-11 | D42516P | 18 | | | D42189J | 3 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2640

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2646 | 286N2646 | | | E5-2 TO LEFT BODY/SPAR INSTALLATION - R2A (continued) | | | | | | | | | | | |
| 0002 | 20 | | GA | | 88-0 | 32-42-11 | D41672P | | 18 | | D42189J | | 3 | | 115-199 |
| 0003 | 20 | | GA | | 104-0 | 32-42-11 | D42516P | | 19 | | D42189J | | 1 | | 001-099 |
| 0003 | 20 | | GA | | 88-0 | 32-42-11 | D41672P | | 19 | | D42189J | | 1 | | 115-199 |
| 0004 | 20 | | GA | | 103-0 | 32-42-11 | D42514P | | 1 | | D41812J | | 9 | | 001-099 |
| 0004 | 20 | | GA | | 89-0 | 32-42-11 | D43014P | | 30 | | D41812J | | 9 | | 115-199 |
| 0005 | 20 | | GA | | 104-0 | 32-42-11 | D42516P | | 17 | | D42189J | | 4 | | 001-099 |
| 0005 | 20 | | GA | | 88-0 | 32-42-11 | D41672P | | 15 | | D42189J | | 4 | | 115-199 |
| 0006 | 20 | | GA | | 104-0 | 32-42-11 | D42516P | | 16 | | D42189J | | 2 | | 001-099 |
| 0006 | 20 | | GA | | 88-0 | 32-42-11 | D41672P | | 16 | | D42189J | | 2 | | 115-199 |
| 0007 | 20 | | GA | | 104-0 | 32-42-12 | D42516P | | 10 | | D41812J | | 3 | | 001-099 |
| 0007 | 20 | | GA | | 88-0 | 32-42-12 | D41672P | | 20 | | D41812J | | 3 | | 115-199 |
| 0008 | 20 | | GA | | 104-0 | 32-42-12 | D42516P | | 11 | | D41812J | | 4 | | 001-099 |
| 0008 | 20 | | GA | | 88-0 | 32-42-12 | D41672P | | 21 | | D41812J | | 4 | | 115-199 |
| 0009 | 20 | | GA | | 104-0 | 32-42-12 | D42516P | | 12 | | D42189J | | 7 | | 001-099 |
| 0009 | 20 | | GA | | 88-0 | 32-42-12 | D41672P | | 22 | | D42189J | | 7 | | 115-199 |
| 0010 | 20 | | GA | | 104-0 | 32-42-12 | D42516P | | 13 | | D42189J | | 8 | | 001-099 |
| 0010 | 20 | | GA | | 88-0 | 32-42-12 | D41672P | | 23 | | D42189J | | 8 | | 115-199 |
| 0011 | 20 | | GA | | 104-0 | 32-42-12 | D42516P | | 14 | | D41812J | | 7 | | 001-099 |
| 0011 | 20 | | GA | | 88-0 | 32-42-12 | D41672P | | 24 | | D41812J | | 7 | | 115-199 |
| 0012 | 20 | | GA | | 104-0 | 32-42-12 | D42516P | | 15 | | D41812J | | 8 | | 001-099 |
| 0012 | 20 | | GA | | 88-0 | 32-42-12 | D41672P | | 25 | | D41812J | | 8 | | 115-199 |
| 0013 | 20 | | GA | | 110-0 | SPARE | D42516P | | 23 | | D40084J | | 18 | | 001-099 |
| 0013 | 20 | | GA | | 95-0 | SPARE | D41672P | | 28 | | D40084J | | 18 | | 115-199 |
| 0014 | 20 | | GA | | 95-0 | SPARE | D41672P | | 29 | | D40084J | | 17 | | 115-199 |
| 0016 | 20 | | GA | | 104-0 | SPARE | D42516P | | 21 | | D41812J | | 16 | | 001-099 |
| 0016 | 20 | | GA | | 88-0 | SPARE | D41672P | | 26 | | D41812J | | 16 | | 115-199 |
| 0017 | 20 | | GA | | 104-0 | SPARE | D42516P | | 22 | | D41812J | | 17 | | 001-099 |
| 0017 | 20 | | GA | | 88-0 | SPARE | D41672P | | 27 | | D41812J | | 17 | | 115-199 |
| 0027 | 20 | | GA | | 104-0 | SPARE | D42516P | | 24 | | D42189J | | 5 | | 001-099 |
| 2501B | 20 | | GU | BA | 110-0 | 32-42-11 | D42516P | | 1 | | D40084J | | 9 | | 001-099 |
| 2501B | 20 | | GU | BA | 95-0 | 32-42-11 | D41672P | | 9 | | D40084J | | 9 | | 115-199 |
| 2501R | 20 | | GU | BA | 0-0 | 32-42-11 | D42516P | | 2 | | D40084J | | 10 | | 001-099 |
| 2501R | 20 | | GU | BA | 0-0 | 32-42-11 | D41672P | | 10 | | D40084J | | 10 | | 115-199 |
| 2501Z | | | | BA | 0-0 | 32-42-11 | D42516P | | 5 | | D40084J | | 7 | | 001-099 |
| 2501Z | | | | BA | 0-0 | 32-42-11 | D41672P | | 4 | | D40084J | | 7 | | 115-199 |
| 2502B | 20 | | GU | BB | 110-0 | 32-42-11 | D42516P | | 3 | | D40084J | | 3 | | 001-099 |
| 2502B | 20 | | GU | BB | 95-0 | 32-42-11 | D41672P | | 3 | | D40084J | | 3 | | 115-199 |
| 2502R | 20 | | GU | BB | 0-0 | 32-42-11 | D42516P | | 4 | | D40084J | | 4 | | 001-099 |
| 2502R | 20 | | GU | BB | 0-0 | 32-42-11 | D41672P | | 5 | | D40084J | | 4 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2640

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2646 | 286N2646 | | | E5-2 TO LEFT BODY/SPAR INSTALLATION - R2A (continued) | | | | | | | | | | | |
| 2502Z | | | | BB | 0-0 | 32-42-11 | D42516P | | 6 | | D40084J | | 6 | | 001-099 |
| 2502Z | | | | BB | 0-0 | 32-42-11 | D41672P | | 6 | | D40084J | | 6 | | 115-199 |
| 2503B | 20 | GU | | BC | 104-0 | 32-42-12 | D42516P | | 8 | | D41812J | | 1 | | 001-099 |
| 2503B | 20 | GU | | BC | 88-0 | 32-42-12 | D41672P | | 11 | | D41812J | | 1 | | 115-199 |
| 2503R | 20 | GU | | BC | 0-0 | 32-42-12 | D42516P | | 9 | | D41812J | | 2 | | 001-099 |
| 2503R | 20 | GU | | BC | 0-0 | 32-42-12 | D41672P | | 12 | | D41812J | | 2 | | 115-199 |
| 2503Z | | | | BC | 0-0 | 32-42-12 | D42516P | | 7 | | D41812J | | 21 | | 001-099 |
| 2503Z | | | | BC | 0-0 | 32-42-12 | D41672P | | 7 | | D41812J | | 21 | | 115-199 |
| 2504B | 20 | GU | | BD | 15-0 | 32-09-12 | D40084J | | 12 | | SP00315 | | 9 | | 001-099 |
| 2504B | 20 | GF | | BD | 15-0 | 32-09-12 | D40084J | | 12 | | SP00315 | | 9 | | 115-199 |
| 2504R | 20 | GU | | BD | 0-0 | 32-09-12 | D40084J | | 11 | | SP00313 | | 9 | | 001-099 |
| 2504R | 20 | GF | | BD | 0-0 | 32-09-12 | D40084J | | 11 | | SP00313 | | 9 | | 115-199 |
| 2504Z | | | | BD | 0-0 | 32-09-12 | D40084J | DED | | | SP00315 | | 9 | | ALL |
| 4501G | 20 | XU | | TA | 95-0 | 32-46-11 | D41672P | | 2 | | D40084J | | 2 | | 115-199 |
| 4501W | 20 | XU | | TA | 0-0 | 32-46-11 | D41672P | | 1 | | D40084J | | 1 | | 115-199 |
| 4502G | 20 | XU | | TB | 95-0 | 32-46-11 | D41672P | | 14 | | D40084J | | 14 | | 115-199 |
| 4502W | 20 | XU | | TB | 0-0 | 32-46-11 | D41672P | | 13 | | D40084J | | 13 | | 115-199 |
| YAAA | | | | | 0-0 | 32-09-12 | D40084J | | S/R | | GD02757 | ST.. | E | | 001-099 |
| YAAA | | | | | 0-0 | 32-42-11 | D40084J | | S/R | | GD02757 | ST.. | E | | 115-199 |
| W2647 | 286N2647 | | | E3-1 TO LEFT MODAL SUPPRESSION ACCELEROMETER - CHANNEL L2 | | | | | | | | | | | |
| 0003 | 22 | GA | | | 137-0 | 22-21-11 | D01357 | | 3 | | D41789P | | 3 | | 001-099 |
| 0003 | 22 | GA | | | 136-0 | 22-21-11 | D01357 | | 3 | | D41789P | | 3 | | 115-199 |
| 0006 | 22 | GA | | | 137-0 | 22-21-11 | D01357 | | 6 | | D41789P | | 6 | | 001-099 |
| 0006 | 22 | GA | | | 136-0 | 22-21-11 | D01357 | | 6 | | D41789P | | 6 | | 115-199 |
| 2001B | 22 | GB | AA | | 137-0 | 22-21-11 | D01357 | | 1 | | D41789P | | 1 | | 001-099 |
| 2001B | 22 | GB | AA | | 136-0 | 22-21-11 | D01357 | | 1 | | D41789P | | 1 | | 115-199 |
| 2001R | 22 | GB | AA | | 0-0 | 22-21-11 | D01357 | | 2 | | D41789P | | 2 | | ALL |
| 2501B | 22 | GU | BA | | 137-0 | 22-21-11 | D01357 | | 5 | | D41789P | | 5 | | 001-099 |
| 2501B | 22 | GU | BA | | 136-0 | 22-21-11 | D01357 | | 5 | | D41789P | | 5 | | 115-199 |
| 2501R | 22 | GU | BA | | 0-0 | 22-21-11 | D01357 | | 4 | | D41789P | | 4 | | ALL |
| 2501Z | | | BA | | 0-0 | 22-21-11 | D01357 | DED | | | D41789P | | 7 | | ALL |
| W2648 | 286N2648 | | | E5-2 TO RIGHT BODY/SPAR INSTALLATION - R2B | | | | | | | | | | | |
| 0001 | 20 | GA | | | 82-0 | SPARE | D42520P | | 7 | | D40434J | | 15 | | 001-099 |
| 0001 | 20 | GA | | | 97-0 | SPARE | D41674P | | 13 | | D40434J | | 15 | | 115-199 |
| 0002 | 20 | GA | | | 97-0 | SPARE | D41674P | | 11 | | D40434J | | 16 | | 115-199 |
| 0003 | 20 | GA | | | 97-0 | SPARE | D41674P | | 12 | | D40434J | | 17 | | 115-199 |
| 2501B | 20 | GU | BA | | 82-0 | 32-42-11 | D42520P | | 1 | | D40434J | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2640

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2648 | 286N2648 | | | E5-2 TO RIGHT BODY/SPAR INSTALLATION - R2B (continued) | | | | | | | | | | | |
| 2501B | 20 | GU | BA | | 97-0 | 32-42-11 | D41674P | | 1 | | D40434J | | 9 | | 115-199 |
| 2501R | 20 | GU | BA | | 0-0 | 32-42-11 | D42520P | | 2 | | D40434J | | 10 | | 001-099 |
| 2501R | 20 | GU | BA | | 0-0 | 32-42-11 | D41674P | | 2 | | D40434J | | 10 | | 115-199 |
| 2501Z | | | BA | | 0-0 | 32-42-11 | D42520P | | 5 | | D40434J | | 7 | | 001-099 |
| 2501Z | | | BA | | 0-0 | 32-42-11 | D41674P | | 5 | | D40434J | | 7 | | 115-199 |
| 2502B | 20 | GU | BB | | 82-0 | 32-42-11 | D42520P | | 3 | | D40434J | | 3 | | 001-099 |
| 2502B | 20 | GU | BB | | 97-0 | 32-42-11 | D41674P | | 3 | | D40434J | | 3 | | 115-199 |
| 2502R | 20 | GU | BB | | 0-0 | 32-42-11 | D42520P | | 4 | | D40434J | | 5 | | 001-099 |
| 2502R | 20 | GU | BB | | 0-0 | 32-42-11 | D41674P | | 4 | | D40434J | | 5 | | 115-199 |
| 2502Z | | | BB | | 0-0 | 32-42-11 | D42520P | | 6 | | D40434J | | 4 | | 001-099 |
| 2502Z | | | BB | | 0-0 | 32-42-11 | D41674P | | 10 | | D40434J | | 4 | | 115-199 |
| 2503B | 20 | GU | BC | | 13-0 | 32-09-12 | D40434J | | 12 | | SP00317 | | 9 | | 001-099 |
| 2503B | 20 | GF | BC | | 13-0 | 32-09-12 | D40434J | | 12 | | SP00317 | | 9 | | 115-199 |
| 2503R | 20 | GU | BC | | 0-0 | 32-09-12 | D40434J | | 11 | | SP00319 | | 9 | | 001-099 |
| 2503R | 20 | GF | BC | | 0-0 | 32-09-12 | D40434J | | 11 | | SP00319 | | 9 | | 115-199 |
| 2503Z | | | BC | | 0-0 | 32-09-12 | D40434J | DED | | | SP00317 | | 9 | | ALL |
| 4501G | 20 | XU | TA | | 97-0 | 32-46-11 | D41674P | | 6 | | D40434J | | 2 | | 115-199 |
| 4501W | 20 | XU | TA | | 0-0 | 32-46-11 | D41674P | | 7 | | D40434J | | 1 | | 115-199 |
| 4502G | 20 | XU | TB | | 97-0 | 32-46-11 | D41674P | | 8 | | D40434J | | 14 | | 115-199 |
| 4502W | 20 | XU | TB | | 0-0 | 32-46-11 | D41674P | | 9 | | D40434J | | 13 | | 115-199 |
| YAAA | | | | | 0-0 | 32-09-12 | D40434J | S/R | | | GD02751 | ST.. | E | | 001-099 |
| YAAA | | | | | 0-0 | 32-42-11 | D40434J | S/R | | | GD02751 | ST.. | E | | 115-199 |
| W2649 | 286N2649 | | | E4-1 TO RIGHT MODAL SUPPRESSION ACCELEROMETER - CHANNEL R2 | | | | | | | | | | | |
| 0003 | 22 | GA | | | 128-0 | 22-21-21 | D01359 | | 3 | | D41791P | | 3 | | 001-099 |
| 0003 | 22 | GA | | | 131-0 | 22-21-21 | D01359 | | 3 | | D41791P | | 3 | | 115-199 |
| 0006 | 22 | GA | | | 128-0 | 22-21-21 | D01359 | | 6 | | D41791P | | 6 | | 001-099 |
| 0006 | 22 | GA | | | 131-0 | 22-21-21 | D01359 | | 6 | | D41791P | | 6 | | 115-199 |
| 2001B | 22 | GB | AA | | 128-0 | 22-21-21 | D01359 | | 1 | | D41791P | | 1 | | 001-099 |
| 2001B | 22 | GB | AA | | 131-0 | 22-21-21 | D01359 | | 1 | | D41791P | | 1 | | 115-199 |
| 2001R | 22 | GB | AA | | 0-0 | 22-21-21 | D01359 | | 2 | | D41791P | | 2 | | ALL |
| 2501B | 22 | GU | BA | | 128-0 | 22-21-21 | D01359 | | 5 | | D41791P | | 5 | | 001-099 |
| 2501B | 22 | GU | BA | | 131-0 | 22-21-21 | D01359 | | 5 | | D41791P | | 5 | | 115-199 |
| 2501R | 22 | GU | BA | | 0-0 | 22-21-21 | D01359 | | 4 | | D41791P | | 4 | | ALL |
| 2501Z | | | BA | | 0-0 | 22-21-21 | D01359 | DED | | | D41791P | | 7 | | ALL |

WIRE LIST

D280N032

91-21-11
Section W2640
Page 5 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2650 | | 286N2650 | | | | E6 RACK TO E/E BAY | | | | | | | | | |
| 0001 | 22 | GA | | | 111-0 | 24-22-41 | D41662P | | 1 | | D41912P | | 1 | | 001-099 |
| 0001 | 22 | GA | | | 131-0 | 24-22-41 | D41662P | | 1 | | SP00208 | | | 9 | 115-199 |
| 0002 | 24 | GK | | | 116-0 | SPARE | D42080P | | 6 | | D41662P | | 24 | | 001-099 |
| 0002 | 24 | GK | | | 146-0 | 36-11-41 | D41684P | | 1 | | D41680P | | 1 | | 115-199 |
| 0003 | 24 | GK | | | 119-0 | 36-11-41 | D41684P | | 2 | | D41662P | | 2 | | 001-099 |
| 0003 | 24 | GK | | | 146-0 | 36-11-41 | D41684P | | 2 | | D41662P | | 2 | | 115-199 |
| 0004 | 20 | GA | | | 119-0 | 36-11-41 | D41684P | | 3 | | D41680P | | 2 | | 001-099 |
| 0004 | 20 | GA | | | 146-0 | 36-11-41 | D41684P | | 3 | | D41680P | | 2 | | 115-199 |
| 0005 | 20 | GA | | | 122-0 | 36-11-41 | D41684P | | 4 | | D41680P | | 3 | | 001-099 |
| 0005 | 20 | GA | | | 146-0 | 36-11-41 | D41684P | | 4 | | D41680P | | 3 | | 115-199 |
| 0006 | 20 | GA | | | 122-0 | 36-11-41 | D41684P | | 5 | | D41680P | | 4 | | 001-099 |
| 0006 | 20 | GA | | | 146-0 | 36-11-41 | D41684P | | 5 | | D41680P | | 4 | | 115-199 |
| 0007 | 20 | GA | | | 122-0 | 36-11-41 | D41684P | | 6 | | D41680P | | 5 | | 001-099 |
| 0007 | 20 | GA | | | 146-0 | 36-11-41 | D41684P | | 6 | | D41680P | | 5 | | 115-199 |
| 0008 | 22 | GA | | | 119-0 | 49-61-11 | D41684P | | 7 | | D41680P | | 6 | | 001-099 |
| 0008 | 22 | GA | | | 146-0 | 49-61-11 | D41684P | | 7 | | D41680P | | 6 | | 115-199 |
| 0009 | 22 | GA | | | 119-0 | 49-61-11 | D41684P | | 8 | | D41680P | | 7 | | 001-099 |
| 0009 | 22 | GA | | | 146-0 | 49-61-11 | D41684P | | 8 | | D41680P | | 7 | | 115-199 |
| 0010 | 22 | GA | | | 113-0 | 49-61-11 | D41660P | | 1 | | D41680P | | 8 | | 001-099 |
| 0010 | 22 | GA | | | 140-0 | 49-61-11 | D41660P | | 1 | | D41680P | | 8 | | 115-199 |
| 0011 | 22 | GA | | | 115-0 | 49-61-11 | D42080P | | 3 | | D41680P | | 9 | | 001-099 |
| 0011 | 22 | GA | | | 140-0 | 49-61-11 | D42080P | | 3 | | D41680P | | 9 | | 115-199 |
| 0012 | 22 | GA | | | 113-0 | 49-61-11 | D41660P | | 3 | | D41662P | | 7 | | 001-099 |
| 0012 | 22 | GA | | | 139-0 | 49-61-11 | D41660P | | 3 | | D41680P | | 10 | | 115-199 |
| 0013 | 22 | GA | | | 113-0 | 49-61-11 | D41660P | | 4 | | D41680P | | 11 | | 001-099 |
| 0013 | 22 | GA | | | 140-0 | 49-61-11 | D41660P | | 4 | | D41680P | | 11 | | 115-199 |
| 0014 | 22 | GA | | | 113-0 | 49-61-11 | D41660P | | 5 | | D41680P | | 12 | | 001-099 |
| 0014 | 22 | GA | | | 140-0 | 49-61-11 | D41660P | | 5 | | D41680P | | 12 | | 115-199 |
| 0015 | 22 | GA | | | 113-0 | 49-61-11 | D41660P | | 6 | | D41680P | | 13 | | 001-099 |
| 0015 | 22 | GA | | | 140-0 | 49-61-11 | D41660P | | 6 | | D41680P | | 13 | | 115-199 |
| 0016 | 22 | GA | | | 113-0 | 49-61-11 | D41660P | | 7 | | D41680P | | 14 | | 001-099 |
| 0016 | 22 | GA | | | 140-0 | 49-61-11 | D41660P | | 7 | | D41680P | | 14 | | 115-199 |
| 0017 | 24 | GK | | | 140-0 | 29-33-11 | D42080P | | 6 | | D41662P | | 24 | | 115-199 |
| 0018 | 22 | GA | | | 139-0 | SPARE | D41660P | | 9 | | D41662P | | 3 | | 115-199 |
| 0020 | 24 | GK | | | 113-0 | 24-34-11 | D41660P | | 11 | | D41680P | | 17 | | 001-099 |
| 0020 | 22 | GA | | | 140-0 | 24-34-11 | D41660P | | 11 | | D41680P | | 17 | | 115-199 |
| 0021 | 22 | GA | | | 113-0 | 49-61-11 | D41660P | | 12 | | D41662P | | 4 | | 001-099 |
| 0021 | 22 | GA | | | 139-0 | 49-61-11 | D41660P | | 12 | | D41662P | | 4 | | 115-199 |
| 0023 | 22 | GA | | | 11-0 | 49-61-11 | D41680P | | 18 | | D41662P | | 5 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2650 | 286N2650 | | | E6 RACK TO E/E BAY (continued) | | | | | | | | | | | |
| 0023 | 22 | | GA | | 10-0 | 49-61-11 | D41680P | | 18 | | D41662P | 5 | | | 115-199 |
| 0024 | 22 | | GA | | 11-0 | 49-61-11 | D41680P | | 19 | | D41662P | 6 | | | 001-099 |
| 0024 | 22 | | GA | | 10-0 | 49-61-11 | D41680P | | 19 | | D41662P | 6 | | | 115-199 |
| 0025 | 22 | | GA | | 10-0 | 49-61-11 | D41680P | | 20 | | D41662P | 7 | | | 115-199 |
| 0026 | 24 | | GK | | 119-0 | 24-27-41 | D41684P | | 9 | | D41662P | 10 | | | 001-099 |
| 0026 | 24 | | GK | | 146-0 | 24-27-41 | D41684P | | 9 | | D41662P | 10 | | | 115-199 |
| 0027 | 22 | | GA | | 11-0 | 49-72-11 | D41680P | | 24 | | D41662P | 9 | | | 001-099 |
| 0027 | 22 | | GA | | 10-0 | 49-72-11 | D41680P | | 24 | | D41662P | 9 | | | 115-199 |
| 0028 | 22 | | GA | | 113-0 | 49-94-11 | D41660P | | 9 | | D41680P | 25 | | | 001-099 |
| 0028 | 22 | | GA | | 140-0 | 49-94-14 | D41660P | | 13 | | D41680P | 25 | | | 115-199 |
| 0029 | 22 | | GA | | 140-0 | 49-94-14 | D41660P | | 14 | | D41680P | 26 | | | 115-199 |
| 0030 | 22 | | GA | | 140-0 | 49-94-14 | D41660P | | 16 | | D41680P | 28 | | | 115-199 |
| 0034 | 22 | | GA | | 11-0 | 49-41-11 | D41680P | | 38 | | D41662P | 22 | | | 001-099 |
| 0034 | 22 | | GA | | 10-0 | 49-41-11 | D41680P | | 38 | | D41662P | 22 | | | 115-199 |
| 0035 | 22 | | GA | | 113-0 | 24-33-12 | D41660P | | 10 | | D41680P | 45 | | | 001-099 |
| 0036 | 16 | | GA | | 3-6 | 49-61-11 | D40170P | | 14 | | D41662P | 15 | | | ALL |
| 0037 | 22 | | GA | | 146-0 | SPARE | D41684P | | 11 | | D41680P | 29 | | | 115-199 |
| 0038 | 22 | | GA | | 113-0 | 24-33-12 | D41660P | | 33 | | D41680P | 22 | | | 001-099 |
| 0039 | 22 | | GA | | 113-0 | 24-33-12 | D41660P | | 23 | | D41680P | 16 | | | 001-099 |
| 0040 | 22 | | GA | | 113-0 | 24-33-12 | D41660P | | 14 | | D41680P | 27 | | | 001-099 |
| 0041 | 22 | | GA | | 119-0 | 49-61-11 | D41684P | | 16 | | D41680P | 51 | | | 001-099 |
| 0041 | 22 | | GA | | 146-0 | 49-61-11 | D41684P | | 16 | | D41680P | 51 | | | 115-199 |
| 0042 | 22 | | GA | | 122-0 | 49-61-11 | D41684P | | 14 | | D41680P | 52 | | | 001-099 |
| 0042 | 22 | | GA | | 146-0 | 49-61-11 | D41684P | | 14 | | D41680P | 52 | | | 115-199 |
| 0043 | 22 | | GA | | 115-0 | 49-61-11 | D41680P | | 40 | | D42080P | 5 | | | 001-099 |
| 0043 | 22 | | GA | | 140-0 | 49-61-11 | D41680P | | 40 | | D42080P | 5 | | | 115-199 |
| 0044 | 22 | | GA | | 115-0 | 49-61-11 | D41680P | | 39 | | D42080P | 4 | | | 001-099 |
| 0044 | 22 | | GA | | 140-0 | 49-61-11 | D41680P | | 39 | | D42080P | 4 | | | 115-199 |
| 0045 | 22 | | GA | | 14-0 | 49-61-11 | D41660P | | 31 | | D42080P | 1 | | | ALL |
| 0046 | 22 | | GA | | 14-0 | 49-61-11 | D41660P | | 30 | | D42080P | 2 | | | 001-099 |
| 0046 | 22 | | GA | | 14-0 | 49-61-11 | D41660P | | 32 | | D42080P | 2 | | | 115-199 |
| 0047 | 22 | | GA | | 11-0 | 49-61-11 | D41680P | | 43 | | D41662P | 16 | | | 001-099 |
| 0047 | 22 | | GA | | 10-0 | 49-61-11 | D41680P | | 43 | | D41662P | 16 | | | 115-199 |
| 0048 | 22 | | GA | | 119-0 | 49-61-11 | D41684P | | 15 | | D41662P | 12 | | | 001-099 |
| 0048 | 22 | | GA | | 146-0 | 49-61-11 | D41684P | | 15 | | D41662P | 12 | | | 115-199 |
| 0050 | 22 | | GA | | 113-0 | 49-61-11 | D41660P | | 29 | | D41680P | 50 | | | 001-099 |
| 0050 | 22 | | GA | | 140-0 | 49-61-11 | D41660P | | 29 | | D41680P | 50 | | | 115-199 |
| 0051 | 22 | | GA | | 113-0 | 49-61-11 | D41660P | | 2 | | D41680P | 42 | | | 001-099 |
| 0051 | 22 | | GA | | 140-0 | 49-61-11 | D41660P | | 2 | | D41680P | 42 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|------------------------------------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2650 | 286N2650 | | | E6 RACK TO E/E BAY (continued) | | | | | | | | | | |
| 0052 | 22 | | GA | | 113-0 | 49-61-11 | D41660P | | 8 | D41662P | | 13 | | 001-099 |
| 0052 | 22 | | GA | | 139-0 | 49-61-11 | D41660P | | 8 | D41662P | | 13 | | 115-199 |
| 0056 | 24 | | GK | | 115-0 | 49-71-11 | D41660P | | 17 | D41662P | | 17 | | 001-099 |
| 0057 | 24 | | GK | | 115-0 | 49-73-11 | D41660P | | 19 | D41662P | | 20 | | 001-099 |
| 0058 | 20 | | GA | | 119-0 | 28-25-11 | D41680P | | 46 | D41684P | | 11 | | 001-099 |
| 0060 | 24 | | GK | | 113-0 | 49-61-14 | D41660P | | 21 | D41680P | | 53 | | 001-099 |
| 0060 | 22 | | GA | | 140-0 | 49-61-14 | D41660P | | 21 | D41680P | | 53 | | 115-199 |
| 0061 | 22 | | GA | | 113-0 | 24-33-12 | D41660P | | 34 | D41680P | | 54 | | 001-099 |
| 0066 | 22 | | GA | | 111-0 | SPARE | D41662P | | 25 | D41912P | | 2 | | 001-099 |
| 0068 | 22 | | GA | | 116-0 | SPARE | D41662P | | 26 | D42080P | | 10 | | 001-099 |
| 0070 | 22 | | GA | | 113-0 | SPARE | D41680P | | 44 | D41660P | | 15 | | 001-099 |
| 0071 | 22 | | GA | | 117-0 | SPARE | D41680P | | 23 | D42080P | | 9 | | 001-099 |
| 0072 | 22 | | GA | | 14-0 | SPARE | D41660P | | 28 | D42080P | | 11 | | 001-099 |
| 0080 | 22 | | GA | | 115-0 | 49-61-11 | D41680P | | 49 | D42080P | | 15 | | 001-099 |
| 2001B | 24 | | GL | AA | 139-0 | 49-71-11 | D41660P | | 17 | D41662P | | 17 | | 115-199 |
| 2001R | 24 | | GL | AA | 0-0 | 49-71-11 | D41660P | | 18 | D41662P | | 18 | | 115-199 |
| 2002B | 24 | | GL | AB | 139-0 | 49-73-11 | D41660P | | 19 | D41662P | | 20 | | 115-199 |
| 2002R | 24 | | GL | AB | 0-0 | 49-73-11 | D41660P | | 20 | D41662P | | 21 | | 115-199 |
| 2003B | 24 | | GL | AC | 122-0 | SPARE | D41684P | | 12 | D41680P | | 30 | | 001-099 |
| 2003B | 24 | | GL | AC | 146-0 | SPARE | D41684P | | 12 | D41680P | | 30 | | 115-199 |
| 2003R | 24 | | GL | AC | 0-0 | SPARE | D41684P | | 13 | D41680P | | 31 | | ALL |
| 2004B | 24 | | GL | AD | 113-0 | 24-34-11 | D41660P | | 24 | D41680P | | 32 | | 001-099 |
| 2004B | 22 | | GB | AD | 140-0 | 24-34-11 | D41660P | | 24 | D41680P | | 32 | | 115-199 |
| 2004R | 24 | | GL | AD | 0-0 | 24-34-11 | D41660P | | 25 | D41680P | | 33 | | 001-099 |
| 2004R | 22 | | GB | AD | 0-0 | 24-34-11 | D41660P | | 25 | D41680P | | 33 | | 115-199 |
| 2501B | 24 | | G2 | DA | 113-0 | 23-41-12 | D41660P | | 26 | D41680P | | 34 | | 001-099 |
| 2501R | 24 | | G2 | DA | 0-0 | 23-41-12 | D41660P | | 27 | D41680P | | 35 | | 001-099 |
| 2501Z | | | | DA | 0-0 | 23-41-12 | D41660P | | 22 | D41680P | | 37 | | 001-099 |
| 3501B | 24 | | G3 | DA | 140-0 | 23-41-12 | D41660P | | 26 | D41680P | | 34 | | 115-199 |
| 3501R | 24 | | G3 | DA | 0-0 | 23-41-12 | D41660P | | 27 | D41680P | | 35 | | 115-199 |
| 3501Y | 24 | | G3 | DA | 0-0 | 23-41-12 | D41660P | | 28 | D41680P | | 36 | | 115-199 |
| 3501Z | | | | DA | 0-0 | 23-41-12 | D41660P | | 22 | D41680P | | 37 | | 115-199 |
| W2651 | 286N2651 | | | DFDAU(E3-3) TO FLIGHT RECORDER(E7) | | | | | | | | | | |
| 0001 | 22 | | GA | | 123-0 | 31-31-01 | D41521P | | 20 | D00013A | | 23 | | 001-099 |
| 0001 | 22 | | GA | | 123-0 | 31-31-13 | D41521P | | 20 | D00013A | | 23 | | 115-199 |
| 0002 | 22 | | GA | | 123-0 | 31-31-01 | D41521P | | 16 | D00013A | | 1 | | 001-099 |
| 0002 | 22 | | GA | | 123-0 | 31-31-13 | D41521P | | 16 | D00013A | | 1 | | 115-199 |
| 0003 | 22 | | GA | | 123-0 | 31-31-13 | D41521P | | 17 | D00013A | CAP | Y | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2651 | 286N2651 | | | | DFDAU(E3-3) TO FLIGHT RECORDER(E7) (continued) | | | | | | | | | | | |
| 0004 | 24 | | GK | | 123-0 | | 31-31-01 | D41521P | | 13 | | D00013A | 21 | | | 001-099 |
| 0004 | 24 | | GK | | 123-0 | | 31-31-13 | D41521P | | 13 | | D00013A | 21 | | | 115-199 |
| 0005 | 24 | | GK | | 123-0 | | 31-31-01 | D41521P | | 14 | | D00013A | 22 | | | 001-099 |
| 0005 | 24 | | GK | | 123-0 | | 31-31-13 | D41521P | | 14 | | D00013A | 22 | | | 115-199 |
| 0006 | 20 | | GA | | 4-0 | | 31-31-01 | GD00180 | DC.. | E | | D00013A | 6 | | | 001-099 |
| 0006 | 20 | | GA | | 4-0 | | 31-31-13 | GD00180 | DC.. | E | | D00013A | 6 | | | 115-199 |
| 0007 | 20 | | GA | | 4-0 | | 31-31-01 | GD00181 | AC.. | E | | D00013A | 2 | | | ALL |
| 0015 | 22 | | GA | | 1-9 | | 31-31-01 | D00013A | | 17 | | GD00179 | ST.. | E | | 010-099 |
| 5001B | 24 | | G2 | AA | 123-0 | | 31-31-01 | D41521P | | 2 | | D00013A | 8 | | | 001-099 |
| 5001B | 24 | | G2 | AA | 123-0 | | 31-31-13 | D41521P | | 2 | | D00013A | 8 | | | 115-199 |
| 5001R | 24 | | G2 | AA | 0-0 | | 31-31-01 | D41521P | | 1 | | D00013A | 7 | | | 001-099 |
| 5001R | 24 | | G2 | AA | 0-0 | | 31-31-13 | D41521P | | 1 | | D00013A | 7 | | | 115-199 |
| 5001Z | | | | AA | 0-0 | | 31-31-01 | D41521P | | 3 | | GD00179 | ST.. | E | | 001-099 |
| 5001Z | | | | AA | 0-0 | | 31-31-13 | D41521P | | 3 | | GD00179 | ST.. | E | | 115-199 |
| 5002B | 24 | | G2 | AB | 123-0 | | 31-31-01 | D41521P | | 8 | | D00013A | 10 | | | 001-099 |
| 5002B | 24 | | G2 | AB | 123-0 | | 31-31-13 | D41521P | | 8 | | D00013A | 10 | | | 115-199 |
| 5002R | 24 | | G2 | AB | 0-0 | | 31-31-13 | D41521P | | 7 | | D00013A | 9 | | | ALL |
| 5002Z | | | | AB | 0-0 | | 31-31-01 | D41521P | | 9 | | GD00179 | ST.. | E | | 001-099 |
| 5002Z | | | | AB | 0-0 | | 31-31-13 | D41521P | | 9 | | GD00179 | ST.. | E | | 115-199 |
| W2653 | 286N2653 | | | | VOICE RECORDER TO E/E RACK... | | | | | | | | | | | |
| 0001 | 20 | | GA | | 133-0 | | 23-71-11 | D00003 | | 2 | | D41561P | 1 | | | ALL |
| 0002 | 20 | | GA | | 4-0 | | 23-71-11 | D00003 | | 3 | | GD00377 | AC.. | E | | 001-099 |
| 0002 | 20 | | GA | | 5-0 | | 23-71-11 | D00003 | | 3 | | GD00377 | AC.. | E | | 115-199 |
| 0003 | 24 | | GK | | 1-0 | | 23-71-11 | D00003 | | 7 | | D00003 | 8 | | | ALL |
| 0004 | 20 | | GA | | 1-0 | | 23-71-11 | D00003 | | 17 | | GD00391 | ST.. | E | | 001-099 |
| 0004 | 20 | | GA | | 5-0 | | 23-71-11 | D00003 | | 17 | | GD00379 | ST.. | E | | 115-199 |
| 0005 | 20 | | GA | | 134-0 | | 23-71-11 | D41561P | | 3 | | GD00391 | ST.. | E | | 001-099 |
| 0005 | 20 | | GA | | 131-0 | | 23-71-11 | D41561P | | 3 | | GD00379 | ST.. | E | | 115-199 |
| 0006 | 22 | | GA | | 133-0 | | 23-71-11 | D00003 | | 14 | | D41561P | 5 | | | ALL |
| 0007 | 24 | | GK | | 133-0 | | 23-71-11 | D00003 | | 13 | | D41561P | 6 | | | ALL |
| 0008 | 24 | | GK | | 133-0 | | 23-71-11 | D00003 | | 15 | | D41561P | 4 | | | ALL |
| 0009 | 24 | | GK | | 133-0 | | 23-71-11 | D00003 | | 16 | | D41561P | 12 | | | ALL |
| 0010 | 24 | | GK | | 133-0 | | 23-71-11 | D00003 | | 12 | | D41561P | 11 | | | ALL |
| 0011 | 22 | | GA | | 133-0 | | 23-71-11 | D00003 | | 57 | | D41561P | 15 | | | ALL |
| 0012 | 22 | | GA | | 133-0 | | 23-71-11 | D00003 | | 55 | | D41561P | 16 | | | ALL |
| 0013 | 24 | | GK | | 133-0 | | 23-71-11 | D00003 | | 23 | | D41561P | 13 | | | 001-099 |
| 2501B | 24 | | G2 | AA | 133-0 | | 23-71-11 | D00003 | | 5 | | D41561P | 20 | | | ALL |
| 2501R | 24 | | G2 | AA | 0-0 | | 23-71-11 | D00003 | | 6 | | D41561P | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|----------|--------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2653 | 286N2653 | VOICE RECORDER TO E/E RACK... (continued) | | | | | | | | | | | | | |
| 2501Z | | AA | 0-0 | 23-71-11 | D00003 | | | AA | D41561P | | | AB | ALL | | |
| 2502B | 24 | G2 | AB | 133-0 | 23-71-11 | D00003 | 45 | | D41561P | 10 | | | ALL | | |
| 2502R | 24 | G2 | AB | 0-0 | 23-71-11 | D00003 | 47 | | D41561P | 21 | | | ALL | | |
| 2502Z | | AB | 0-0 | 23-71-11 | D00003 | | | AA | D41561P | | | AB | ALL | | |
| 2503B | 24 | G2 | AC | 133-0 | 23-71-11 | D00003 | 41 | | D41561P | 17 | | | ALL | | |
| 2503R | 24 | G2 | AC | 0-0 | 23-71-11 | D00003 | 43 | | D41561P | 7 | | | ALL | | |
| 2503Z | | AC | 0-0 | 23-71-11 | D00003 | | | AA | D41561P | | | AB | ALL | | |
| 2504B | 24 | G2 | AD | 133-0 | 23-71-11 | D00003 | 35 | | D41561P | 2 | | | ALL | | |
| 2504R | 24 | G2 | AD | 0-0 | 23-71-11 | D00003 | 37 | | D41561P | 8 | | | ALL | | |
| 2504Z | | AD | 0-0 | 23-71-11 | D00003 | | | AA | D41561P | | | AB | ALL | | |
| 2505B | 24 | G2 | AE | 133-0 | 23-71-11 | D00003 | 30 | | D41561P | 19 | | | ALL | | |
| 2505R | 24 | G2 | AE | 0-0 | 23-71-11 | D00003 | 32 | | D41561P | 18 | | | ALL | | |
| 2505Z | | AE | 0-0 | 23-71-11 | D00003 | | | AA | D41561P | | | AB | ALL | | |
| 2506B | 24 | G2 | AF | 133-0 | 23-71-11 | D00003 | 25 | | D41561P | 25 | | | 001-099 | | |
| 2506R | 24 | G2 | AF | 0-0 | 23-71-11 | D00003 | 24 | | D41561P | 24 | | | 001-099 | | |
| 2506Z | | AF | 0-0 | 23-71-11 | D00003 | | | AA | D41561P | | | AB | 001-099 | | |
| FRAA | | | 0-0 | 23-71-11 | D00003 | | | AA | GD00381 | ST.. | E | | ALL | | |
| FRAB | | | 0-0 | 23-71-11 | D41561P | | | AB | D41561P | 22 | | | ALL | | |
| W2654 | 286N2654 | APU COMPARTMENT TO E6-2 AND E6 RELAY PNL | | | | | | | | | | | | | |
| 0001 | 20 | GA | 6-0 | 49-14-11 | D40198J | 4 | | | GD00339 | DC.. | E | | 001-002 | | |
| 0001 | 20 | GA | 6-0 | 49-14-11 | D40198J | 4 | | | GD00339 | DC.. | E | * | 003-099 | | |
| 0001 | 20 | GA | 4-0 | 49-14-11 | D40198J | 4 | | | GD00339 | DC.. | E | | 115-199 | | |
| 0002 | 20 | GA | 6-0 | 49-14-11 | D40198J | 17 | | | GD00339 | DC.. | E | | 001-002 | | |
| 0002 | 20 | GA | 6-0 | 49-14-11 | D40198J | 17 | | | GD00339 | DC.. | E | * | 003-099 | | |
| 0002 | 20 | GA | 4-0 | 49-14-11 | D40198J | 17 | | | GD00339 | DC.. | E | | 115-199 | | |
| 0003 | 20 | GA | 46-0 | 49-14-11 | D41676P | 1 | | | D40198J | 13 | | | 001-099 | | |
| 0003 | 20 | GA | 32-0 | 49-14-11 | D41676P | 1 | | | D40198J | 13 | | | 115-199 | | |
| 0004 | 20 | GA | 46-0 | 49-14-11 | D41676P | 2 | | | D40198J | 1 | | | 001-099 | | |
| 0004 | 20 | GA | 32-0 | 49-14-11 | D41676P | 2 | | | D40198J | 1 | | | 115-199 | | |
| 0005 | 20 | GA | 46-0 | 49-14-11 | D41676P | 3 | | | D40198J | 2 | | | 001-099 | | |
| 0005 | 20 | GA | 32-0 | 49-14-11 | D41676P | 3 | | | D40198J | 2 | | | 115-199 | | |
| 0006 | 20 | GA | 46-0 | 49-14-11 | D41676P | 4 | | | D40198J | 3 | | | 001-099 | | |
| 0006 | 20 | GA | 32-0 | 49-14-11 | D41676P | 4 | | | D40198J | 3 | | | 115-199 | | |
| 0007 | 20 | GA | 46-0 | 49-14-11 | D41676P | 5 | | | D40198J | 16 | | | 001-099 | | |
| 0007 | 20 | GA | 32-0 | 49-14-11 | D41676P | 5 | | | D40198J | 16 | | | 115-199 | | |
| 0008 | 20 | GA | 46-0 | 49-14-11 | D41676P | 6 | | | D40198J | 7 | | | 001-099 | | |
| 0008 | 20 | GA | 32-0 | 49-14-11 | D41676P | 6 | | | D40198J | 7 | | | 115-199 | | |
| 0009 | 20 | GA | 46-0 | 49-14-11 | D41676P | 7 | | | D40198J | 8 | | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2654 | 286N2654 | | | APU COMPARTMENT TO E6-2 AND E6 RELAY PNL (continued) | | | | | | | | | | | |
| 0009 | 20 | | GA | | 32-0 | 49-14-11 | D41676P | 7 | | | D40198J | 8 | | | 115-199 |
| 0010 | 20 | | GA | | 46-0 | 49-14-11 | D41676P | 8 | | | D40198J | 9 | | | 001-099 |
| 0010 | 20 | | GA | | 32-0 | 49-14-11 | D41676P | 8 | | | D40198J | 9 | | | 115-199 |
| 0011 | 20 | | GA | | 6-0 | 49-14-11 | GD00339 | DC.. | E | | D40198J | 10 | | | 001-002 |
| 0011 | 20 | | GA | | 6-0 | 49-14-11 | GD00339 | DC.. | E | * | D40198J | 10 | | | 003-099 |
| 0011 | 20 | | GA | | 4-0 | 49-14-11 | GD00339 | DC.. | E | | D40198J | 10 | | | 115-199 |
| 0012 | 20 | | GA | | 46-0 | 49-14-11 | D41676P | 10 | | | D40198J | 5 | | | 001-099 |
| 0012 | 20 | | GA | | 32-0 | 49-14-11 | D41676P | 10 | | | D40198J | 5 | | | 115-199 |
| 0013 | 20 | | GA | | 46-0 | 49-14-11 | D41676P | 11 | | | D40198J | 6 | | | 001-099 |
| 0013 | 20 | | GA | | 32-0 | 49-14-11 | D41676P | 11 | | | D40198J | 6 | | | 115-199 |
| 0014 | 20 | | GA | | 46-0 | 49-14-11 | D41676P | 12 | | | D40198J | 19 | | | 001-099 |
| 0014 | 20 | | GA | | 32-0 | 49-14-11 | D41676P | 12 | | | D40198J | 19 | | | 115-199 |
| 0015 | 20 | | GA | | 46-0 | 49-14-11 | D41676P | 13 | | | D40198J | 20 | | | 001-099 |
| 0015 | 20 | | GA | | 32-0 | 49-14-11 | D41676P | 13 | | | D40198J | 20 | | | 115-199 |
| 0017 | 18 | | GA | | 4-0 | 36-11-41 | D01616 | 3 | | | GD00337 | AC.. | E | | 001-099 |
| 0017 | 20 | | GA | | 3-0 | 36-11-41 | D01616 | 3 | | | GD00337 | AC.. | E | | 115-199 |
| 0018 | 18 | | GA | | 4-0 | 36-11-41 | D01616 | 5 | | | GD00335 | DC.. | E | | 001-099 |
| 0018 | 20 | | GA | | 3-0 | 36-11-41 | D01616 | 5 | | | GD00335 | DC.. | E | | 115-199 |
| 0019 | 18 | | GA | | 55-0 | 36-11-41 | D41688P | 3 | 18 | | D01616 | 4 | | | 001-099 |
| 0019 | 20 | | GA | | 44-0 | 36-11-41 | D41688P | 3 | | | D01616 | 4 | | | 115-199 |
| 0020 | 18 | | GA | | 55-0 | 36-11-41 | D41688P | 5 | 18 | | D01616 | 1 | | | 001-099 |
| 0020 | 20 | | GA | | 44-0 | 36-11-41 | D41688P | 5 | | | D01616 | 1 | | | 115-199 |
| 0021 | 18 | | GA | | 55-0 | 36-11-41 | D41688P | 7 | 18 | | D01616 | 2 | | | 001-099 |
| 0021 | 20 | | GA | | 44-0 | 36-11-41 | D41688P | 7 | | | D01616 | 2 | | | 115-199 |
| 0022 | 18 | | GA | | 55-0 | 36-11-41 | D41688P | 9 | 18 | | D01616 | 7 | | | 001-099 |
| 0022 | 20 | | GA | | 44-0 | 36-11-41 | D41688P | 9 | | | D01616 | 7 | | | 115-199 |
| 0023 | 18 | | GA | | 4-0 | 36-11-41 | D01616 | 6 | | | GD00335 | DC.. | E | | 001-099 |
| 0023 | 20 | | GA | | 3-0 | 36-11-41 | D01616 | 6 | | | GD00335 | DC.. | E | | 115-199 |
| 0024 | 16 | | GA | | 3-0 | 49-61-14 | D02618 | 3 | | | GD00448 | ST.. | E | | 001-099 |
| 0024 | 16 | | GA | | 2-0 | 49-61-14 | D02618 | 3 | | | GD00448 | ST.. | E | | 115-199 |
| 0025 | 18 | | GA | | 48-0 | 49-61-14 | D41688P | 1 | | | D02618 | 7 | | | 001-099 |
| 0025 | 18 | | GA | | 36-0 | 49-61-14 | D41688P | 1 | | | D02618 | 7 | | | 115-199 |
| 0026 | 18 | | GA | | 48-0 | 49-61-14 | D41688P | 2 | | | D02618 | 5 | | | 001-099 |
| 0026 | 18 | | GA | | 36-0 | 49-61-14 | D41688P | 2 | | | D02618 | 5 | | | 115-199 |
| 0027 | 18 | | GA | | 2-0 | 49-61-14 | D02618 | 6 | | | GD00341 | DC.. | E | | ALL |
| 0028 | 20 | | GA | | 54-0 | 49-61-14 | D41676P | 14 | | | SP00206 | | 9 | | 001-099 |
| 0028 | 20 | | GA | | 41-0 | 49-61-14 | D41676P | 14 | | | SP00206 | | 9 | | 115-199 |
| 0029 | 18 | | GA | | 2-0 | 49-61-14 | D02618 | 10 | | | GD00341 | DC.. | E | | ALL |
| 0030 | 20 | | GA | | 5-0 | 33-31-31 | D40104J | 2 | | | SP00204 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|--|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---|---------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2654 | 286N2654 | | | APU COMPARTMENT TO E6-2 AND E6 RELAY PNL (continued) | | | | | | | | | | | | |
| 0031 | 18 | | GA | 2-0 | 49-61-14 | D02618 | | | 1 | | | GD00341 | DC.. | E | | 001-099 |
| 0031 | 18 | | GA | 3-0 | 49-61-14 | D02618 | | | 1 | | | GD00341 | DC.. | E | | 115-199 |
| 0032 | 20 | | GA | 36-0 | 49-94-14 | D41688P | | | 13 | | | D40198J | 21 | | | 115-199 |
| 0033 | 20 | | GA | 36-0 | 49-94-14 | D41688P | | | 14 | | | D40198J | 22 | | | 115-199 |
| 0034 | 20 | | GA | 36-0 | 49-94-14 | D41688P | | | 15 | | | D40198J | 23 | | | 115-199 |
| 0036 | 18 | | GA | 8-0 | 33-31-31 | D40104J | | | 7 | | | GD00591 | AC.. | E | | 001-099 |
| 0036 | 18 | | GA | 5-0 | 33-31-31 | D40104J | | | 7 | | | GD00591 | AC.. | E | | 115-199 |
| 0037 | 20 | | GA | 48-0 | 49-94-11 | D40198J | | | 14 | | | D41688P | 13 | | | 001-099 |
| 0037 | 20 | | GA | 32-0 | SPARE | D40198J | | | 14 | | | D41676P | 16 | | | 115-199 |
| 0041 | 20 | | GA | 46-0 | SPARE | D40198J | | | 18 | | | D41678P | 15 | | | 001-099 |
| 0041 | 20 | | GA | 33-0 | SPARE | D40198J | | | 18 | | | D41678P | 15 | | | 115-199 |
| 0042 | 20 | | GA | 46-0 | SPARE | D41676P | | | 17 | | | D40200J | 22 | | | 001-099 |
| 0042 | 20 | | GA | 32-0 | SPARE | D41676P | | | 17 | | | D40200J | 22 | | | 115-199 |
| 0043 | 20 | | GA | 46-0 | SPARE | D41676P | | | 18 | | | D40200J | 28 | | | 001-099 |
| 0043 | 20 | | GA | 32-0 | SPARE | D41676P | | | 18 | | | D40200J | 28 | | | 115-199 |
| 0044 | 20 | | GA | 46-0 | SPARE | D41676P | | | 41 | | | D40200J | 29 | | | 001-099 |
| 0044 | 20 | | GA | 32-0 | SPARE | D41676P | | | 41 | | | D40200J | 29 | | | 115-199 |
| 0045 | 24 | | GK | 48-0 | 49-61-14 | D02618 | | | 8 | | | D41688P | 4 | | | 001-099 |
| 0045 | 24 | | GK | 36-0 | 49-61-14 | D02618 | | | 8 | | | D41688P | 4 | | | 115-199 |
| 0046 | 24 | | GK | 48-0 | 49-61-14 | D02618 | | | 4 | | | D41688P | 6 | | | 001-099 |
| 0046 | 24 | | GK | 36-0 | 49-61-14 | D02618 | | | 4 | | | D41688P | 6 | | | 115-199 |
| 0047 | 20 | | GA | 48-0 | SPARE | D41688P | | | 22 | | | D40198J | 24 | | | 001-099 |
| 0047 | 20 | | GA | 36-0 | SPARE | D41688P | | CAP | Y | | | D40198J | 24 | | | 115-199 |
| 0048 | 20 | | GA | 48-0 | SPARE | D41688P | | | 14 | | | D40198J | 25 | | | 001-099 |
| 0048 | 20 | | GA | 36-0 | SPARE | D41688P | | | 11 | | | D40198J | 25 | | | 115-199 |
| 0049 | 20 | | GA | 6-0 | 49-94-11 | D40198J | | | 15 | | | GD00339 | DC.. | E | | 001-002 |
| 0049 | 20 | | GA | 6-0 | 49-94-11 | D40198J | | | 15 | | | GD00339 | DC.. | E | * | 003-099 |
| 0049 | 20 | | GA | 32-0 | SPARE | D40198J | | | 15 | | | D41676P | 15 | | | 115-199 |
| 2501B | 20 | | GU | 46-0 | 49-14-11 | D41678P | | | 1 | | | D40200J | 16 | | | 001-099 |
| 2501B | 20 | | GU | 33-0 | 49-14-11 | D41678P | | | 1 | | | D40200J | 16 | | | 115-199 |
| 2501R | 20 | | GU | 0-0 | 49-14-11 | D41678P | | | 2 | | | D40200J | 17 | | | ALL |
| 2501Z | | | | 0-0 | 49-14-11 | D41678P | | | | | AC | D40200J | 31 | | | ALL |
| 2502B | 20 | | GU | 46-0 | 49-14-11 | D41678P | | | 3 | | | D40200J | 37 | | | 001-099 |
| 2502B | 20 | | GU | 33-0 | 49-14-11 | D41678P | | | 3 | | | D40200J | 37 | | | 115-199 |
| 2502R | 20 | | GU | 0-0 | 49-14-11 | D41678P | | | 4 | | | D40200J | 38 | | | ALL |
| 2502Z | | | | 0-0 | 49-14-11 | D41678P | | | | | AC | D40200J | 30 | | | ALL |
| 2503B | 20 | | GU | 46-0 | 49-14-11 | D41678P | | | 5 | | | D40198J | 11 | | | 001-099 |
| 2503B | 20 | | GU | 33-0 | 49-14-11 | D41678P | | | 5 | | | D40198J | 11 | | | 115-199 |
| 2503R | 20 | | GU | 0-0 | 49-14-11 | D41678P | | | 6 | | | D40198J | 12 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2654 | 286N2654 | | | APU COMPARTMENT TO E6-2 AND E6 RELAY PNL (continued) | | | | | | | | | | | |
| 2503Z | | | | BC | 0-0 | 49-14-11 | D41678P | | | AC | D40198J | DED | | | ALL |
| 2504B | 20 | GU | BD | | 46-0 | 49-14-11 | D41676P | 19 | | | D40200J | 3 | | | 001-099 |
| 2504B | 20 | GU | BD | | 32-0 | 49-14-11 | D41676P | 19 | | | D40200J | 3 | | | 115-199 |
| 2504R | 20 | GU | BD | | 0-0 | 49-14-11 | D41676P | 20 | | | D40200J | 4 | | | ALL |
| 2504Z | | | | BD | 0-0 | 49-14-11 | D41676P | | | AA | D40200J | DED | | | ALL |
| 2505B | 20 | GU | BE | | 46-0 | 49-14-11 | D41676P | 21 | | | D40200J | 5 | | | 001-099 |
| 2505B | 20 | GU | BE | | 32-0 | 49-14-11 | D41676P | 21 | | | D40200J | 5 | | | 115-199 |
| 2505R | 20 | GU | BE | | 0-0 | 49-14-11 | D41676P | 22 | | | D40200J | 6 | | | ALL |
| 2505Z | | | | BE | 0-0 | 49-14-11 | D41676P | | | AA | D40200J | DED | | | ALL |
| 2506B | 20 | GU | BF | | 46-0 | 49-14-11 | D41676P | 23 | | | D40200J | 14 | | | 001-099 |
| 2506B | 20 | GU | BF | | 32-0 | 49-14-11 | D41676P | 23 | | | D40200J | 14 | | | 115-199 |
| 2506R | 20 | GU | BF | | 0-0 | 49-14-11 | D41676P | 24 | | | D40200J | 15 | | | ALL |
| 2506Z | | | | BF | 0-0 | 49-14-11 | D41676P | | | AA | D40200J | DED | | | ALL |
| 2507B | 20 | GU | BG | | 46-0 | 49-14-11 | D41676P | 25 | | | D40200J | 1 | | | 001-099 |
| 2507B | 20 | GU | BG | | 32-0 | 49-14-11 | D41676P | 25 | | | D40200J | 1 | | | 115-199 |
| 2507R | 20 | GU | BG | | 0-0 | 49-14-11 | D41676P | 26 | | | D40200J | 2 | | | ALL |
| 2507Z | | | | BG | 0-0 | 49-14-11 | D41676P | | | AA | D40200J | DED | | | ALL |
| 2508B | 20 | GU | BH | | 46-0 | 49-14-11 | D41676P | 27 | | | D40200J | 7 | | | 001-099 |
| 2508B | 20 | GU | BH | | 32-0 | 49-14-11 | D41676P | 27 | | | D40200J | 7 | | | 115-199 |
| 2508R | 20 | GU | BH | | 0-0 | 49-14-11 | D41676P | 28 | | | D40200J | 8 | | | ALL |
| 2508Z | | | | BH | 0-0 | 49-14-11 | D41676P | | | AA | D40200J | DED | | | ALL |
| 2509B | 20 | GU | BI | | 46-0 | 49-14-11 | D41676P | 30 | | | D40200J | 12 | | | 001-099 |
| 2509B | 20 | GU | BI | | 32-0 | 49-14-11 | D41676P | 30 | | | D40200J | 12 | | | 115-199 |
| 2509R | 20 | GU | BI | | 0-0 | 49-14-11 | D41676P | 31 | | | D40200J | 26 | | | ALL |
| 2509Z | | | | BI | 0-0 | 49-14-11 | D41676P | | | AB | D40200J | DED | | | ALL |
| 2510B | 20 | GU | BJ | | 46-0 | 49-14-11 | D41676P | 32 | | | D40200J | 13 | | | 001-099 |
| 2510B | 20 | GU | BJ | | 32-0 | 49-14-11 | D41676P | 32 | | | D40200J | 13 | | | 115-199 |
| 2510R | 20 | GU | BJ | | 0-0 | 49-14-11 | D41676P | 33 | | | D40200J | 27 | | | ALL |
| 2510Z | | | | BJ | 0-0 | 49-14-11 | D41676P | | | AB | D40200J | DED | | | ALL |
| 2511B | 20 | GU | AO | | 46-0 | SPARE | D40200J | 19 | | | D41678P | 12 | | | 001-099 |
| 2511B | 20 | GU | AA | | 33-0 | SPARE | D40200J | 19 | | | D41678P | 12 | | | 115-199 |
| 2511R | 20 | GU | AO | | 0-0 | SPARE | D40200J | 20 | | | D41678P | 13 | | | 001-099 |
| 2511R | 20 | GU | AA | | 0-0 | SPARE | D40200J | 20 | | | D41678P | 13 | | | 115-199 |
| 2511Z | | | | AO | 0-0 | SPARE | D40200J | 21 | | | D41678P | DED | | | 001-099 |
| 2511Z | | | | AA | 0-0 | SPARE | D40200J | 21 | | | D41678P | DED | | | 115-199 |
| 2512B | 20 | GU | DA | | 31-0 | 23-41-12 | D41688P | 12 | | | SM00001 | | 9 | | 001-099 |
| 2512R | 20 | GU | DA | | 0-0 | 23-41-12 | D41688P | 11 | | | SM00002 | | 9 | | 001-099 |
| 2512Z | | | | DA | 0-0 | 23-41-12 | D41688P | 8 | | | SM00004 | | 9 | | 001-099 |
| 2513B | 20 | GU | DB | | 18-0 | 23-41-12 | D40104J | 3 | | | SM00001 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2654 | 286N2654 | | | APU COMPARTMENT TO E6-2 AND E6 RELAY PNL (continued) | | | | | | | | | | | |
| 2513R | 20 | GU | DB | | 0-0 | 23-41-12 | D40104J | 4 | | | SM00002 | | 9 | | 001-099 |
| 2513Z | | | DB | | 0-0 | 23-41-12 | D40104J | 1 | | | SM00004 | | 9 | | 001-099 |
| 2514B | 20 | GU | DC | | 11-0 | 23-41-12 | SM00001 | | 9 | | SM00006 | | 9 | | 001-099 |
| 2514R | 20 | GU | DC | | 0-0 | 23-41-12 | SM00002 | | 9 | | SM00007 | | 9 | | 001-099 |
| 2514Z | | | DC | | 0-0 | 23-41-12 | SM00004 | | 9 | | SM00005 | | 9 | | 001-099 |
| 3501B | 20 | GV | DA | | 20-0 | 23-41-12 | D41688P | 17 | | | SM00001 | | 9 | | 115-199 |
| 3501R | 20 | GV | DA | | 0-0 | 23-41-12 | D41688P | 18 | | | SM00002 | | 9 | | 115-199 |
| 3501Y | 20 | GV | DA | | 0-0 | 23-41-12 | D41688P | 19 | | | SM00003 | | 9 | | 115-199 |
| 3501Z | | | DA | | 0-0 | 23-41-12 | D41688P | 20 | | | SM00004 | | 9 | | 115-199 |
| 3502B | 20 | GV | DB | | 20-0 | 23-41-12 | D40104J | 3 | | | SM00001 | | 9 | | 115-199 |
| 3502R | 20 | GV | DB | | 0-0 | 23-41-12 | D40104J | 4 | | | SM00002 | | 9 | | 115-199 |
| 3502Y | 20 | GV | DB | | 0-0 | 23-41-12 | D40104J | 5 | | | SM00003 | | 9 | | 115-199 |
| 3502Z | | | DB | | 0-0 | 23-41-12 | D40104J | 1 | | | SM00004 | | 9 | | 115-199 |
| 3503B | 20 | GV | DC | | 10-0 | 23-41-12 | SM00001 | | 9 | | SM00006 | | 9 | | 115-199 |
| 3503R | 20 | GV | DC | | 0-0 | 23-41-12 | SM00002 | | 9 | | SM00007 | | 9 | | 115-199 |
| 3503Y | 20 | GV | DC | | 0-0 | 23-41-12 | SM00003 | | 9 | | SM00005 | | 9 | | 115-199 |
| 3503Z | | | DC | | 0-0 | 23-41-12 | SM00004 | | 9 | | SM00005 | DED | | | 115-199 |
| 4251B | 20 | GW | FA | | 46-0 | 49-14-11 | D41678P | 8 | | | D40200J | 34 | | | 001-099 |
| 4251B | 20 | GW | FA | | 33-0 | 49-14-11 | D41678P | 8 | | | D40200J | 34 | | | 115-199 |
| 4251G | 20 | GW | FA | | 0-0 | 49-14-11 | D41678P | 9 | | | D40200J | 32 | | | ALL |
| 4251R | 20 | GW | FA | | 0-0 | 49-14-11 | D41678P | 10 | | | D40200J | 18 | | | ALL |
| 4251Y | 20 | GW | FA | | 0-0 | 49-14-11 | D41678P | 11 | | | D40200J | 35 | | | ALL |
| 4251Z | | | FA | | 0-0 | 49-14-11 | D41678P | | | AC | D40200J | 33 | | | ALL |
| 4501G | 20 | DU | XA | | 46-0 | 49-14-11 | D41676P | 34 | TC | | D40200J | 10 | 4B | | 001-099 |
| 4501G | 20 | DU | XA | | 32-0 | 49-14-11 | D41676P | 34 | | | D40200J | 10 | 4B | | 115-199 |
| 4501W | 20 | DU | XA | | 0-0 | 49-14-11 | D41676P | 35 | TD | | D40200J | 24 | 4D | | 001-099 |
| 4501W | 20 | DU | XA | | 0-0 | 49-14-11 | D41676P | 35 | | | D40200J | 24 | 4D | | 115-199 |
| 4501Z | | | XA | | 0-0 | 49-14-11 | D41676P | | | AB | D40200J | 41 | | | ALL |
| 4502G | 20 | DU | XB | | 46-0 | 49-14-11 | D41676P | 36 | TC | | D40200J | 11 | 4B | | 001-099 |
| 4502G | 20 | DU | XB | | 32-0 | 49-14-11 | D41676P | 36 | | | D40200J | 11 | 4B | | 115-199 |
| 4502W | 20 | DU | XB | | 0-0 | 49-14-11 | D41676P | 37 | TD | | D40200J | 25 | 4D | | 001-099 |
| 4502W | 20 | DU | XB | | 0-0 | 49-14-11 | D41676P | 37 | | | D40200J | 25 | 4D | | 115-199 |
| 4502Z | | | XB | | 0-0 | 49-14-11 | D41676P | | | AB | D40200J | 42 | | | ALL |
| 4503G | 20 | DU | XC | | 46-0 | 49-14-11 | D41676P | 38 | TC | | D40200J | 9 | 4B | | 001-099 |
| 4503G | 20 | DU | XC | | 32-0 | 49-14-11 | D41676P | 38 | | | D40200J | 9 | 4B | | 115-199 |
| 4503W | 20 | DU | XC | | 0-0 | 49-14-11 | D41676P | 39 | TD | | D40200J | 23 | 4D | | 001-099 |
| 4503W | 20 | DU | XC | | 0-0 | 49-14-11 | D41676P | 39 | | | D40200J | 23 | 4D | | 115-199 |
| 4503Z | | | XC | | 0-0 | 49-14-11 | D41676P | | | AB | D40200J | 40 | | | ALL |
| A-A | | | | | 0-0 | 49-61-14 | S10031 | | R | | SP00206 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2650

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2654 | 286N2654 | | | APU COMPARTMENT TO E6-2 AND E6 RELAY PNL (continued) | | | | | | | | | | | |
| A-B | | | | | 0-0 | 49-61-14 | S10031 | | B | | GD00333 | DC.. | E | | ALL |
| A-CA | | | | ZA | 0-0 | 23-41-12 | D00429 | | BLK | | SM00005 | | 9 | | ALL |
| A-CB | | | | ZA | 0-0 | 23-41-12 | D00429 | | BLU | | SM00006 | | 9 | | ALL |
| A-CC | | | | ZA | 0-0 | 23-41-12 | D00429 | | RED | | SM00007 | | 9 | | ALL |
| FRAA | | | | | 0-0 | 49-14-11 | D41676P | | 29 | | D41676P | | | AA | ALL |
| FRAB | | | | | 0-0 | 49-14-11 | D41676P | | 40 | | D41676P | | | AB | ALL |
| FRAC | | | | | 0-0 | 49-14-11 | D41678P | | 7 | | D41678P | | | AC | ALL |
| W2658 | 286N2658 | | | E6 RACK TO L. W/WELL-APU SOV | | | | | | | | | | | |
| 0001 | 20 | | GA | | 69-3 | 28-25-21 | D41770P | | 1 | | D02382 | | 3 | | 001-099 |
| 0001 | 20 | | GA | | 79-0 | 28-25-21 | D41770P | | 1 | | D02382 | | 3 | | 115-199 |
| 0003 | 20 | | GA | | 69-3 | 28-25-21 | D41770P | | 3 | | D02382 | | 5 | | 001-099 |
| 0003 | 20 | | GA | | 79-0 | 28-25-21 | D41770P | | 3 | | D02382 | | 5 | | 115-199 |
| 0004 | 20 | | GA | | 69-3 | 28-25-21 | D41770P | | 4 | | D02382 | | 2 | | 001-099 |
| 0004 | 20 | | GA | | 79-0 | 28-25-21 | D41770P | | 4 | | D02382 | | 2 | | 115-199 |
| 0005 | 18 | | GA | | 1-7 | 28-25-21 | GD01867 | | ST.. | E | D02382 | | 7 | | 001-099 |
| 0005 | 18 | | GA | | 3-0 | 28-25-21 | GD01867 | | ST.. | E | D02382 | | 7 | | 115-199 |
| 0006 | 18 | | GA | | 1-11 | 28-25-21 | GD01866 | | DC.. | E | D02382 | | 4 | | 001-099 |
| 0006 | 18 | | GA | | 2-0 | 28-25-21 | GD01866 | | DC.. | E | D02382 | | 4 | | 115-199 |
| YAAA | | | | | 0-0 | 28-25-21 | GD01659 | | ST.. | E | GD01867 | ST.. | E | | ALL |
| W2659 | 286N2659 | | | VHF-C COAX, E4-4 TO ANT DISC | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-12-31 | D41719J | | = C1 | | D41029J | | = C1 | | 001-099 |
| 001CX | | | | BS AA | 96-0 | 23-12-31 | D41719J | | = A1 | | D41029J | | = A1 | | 001-099 |

WIRE LIST

D280N032

91-21-11
Section W2650
Page 10 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|-----------------------------------|------------------------|------------------------|-------------|
| Wire No. | GA CO TY | Fam FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W2661 | 286N2661 | MARKER BEACON-L TO ANTENNA | | | |
| 001CO | | AA 0-0 34-32-11 | D41749P =C1 | D00209 =C1 | 001-099 |
| 001CO | | AA 0-0 34-32-11 | D41917P =C1 | D00209 =C1 | 115-199 |
| 001CX | BS | AA 21-0 34-32-11 | D41749P =A1 | D00209 =A1 | 001-099 |
| 001CX | BS | AA 121-0 34-32-11 | D41917P =A1 | D00209 =A1 | 115-199 |
| W2662 | 286N2662 | E6 TO AFT CARGO BAY | | | |
| 0001 | 18 | GA 56-0 25-51-21 | D42032P 1 | D02468 1 | 115-199 |
| 0002 | 18 | GA 56-0 25-51-21 | D42032P 2 | D02468 2 | 115-199 |
| 0003 | 18 | GA 56-0 25-51-21 | D42032P 3 | D02468 3 | 115-199 |
| 0004 | 20 | GA 56-0 25-51-21 | D41932P 1 | D02468 6 | 115-199 |
| 0005 | 16 | GA 5-0 25-51-21 | D02468 8 | GD00138 ST.. E | 115-199 |
| 0006 | 20 | GA 33-0 25-51-21 | D41932P 11 | S10207 3 C | 115-199 |
| 0007 | 20 | GA 33-0 25-51-21 | D41932P 3 | S10207 1 C | 115-199 |
| 0008 | 20 | GA 31-0 25-51-21 | D04748 2 | SM00004 9 | 115-199 |
| 0009 | 20 | GA 48-0 25-51-21 | D41932P 5 | S10212 C C | 115-199 |
| 0010 | 20 | GA 37-0 25-51-21 | D41932P 6 | SP00202 9 | 115-199 |
| 0012 | 18 | GA 25-4 33-37-21 | C04047 =L D | L00224 =P C * | 001-099 |
| 0012 | 18 | GA 43-0 33-37-21 | C04047 =L D | L00224 =P C * | 115-199 |
| 0013 | 20 | GA 18-11 33-37-21 | L00224 =P C * | L00225 =P C * | 001-099 |
| 0013 | 20 | GA 20-0 33-37-21 | L00224 =P C * | L00225 =P C * | 115-199 |
| 0014 | 20 | GA 15-7 33-37-21 | L00225 =P C * | L00226 =P C * | 001-099 |
| 0014 | 20 | GA 17-0 33-37-21 | L00225 =P C * | L00226 =P C * | 115-199 |
| 0015 | 20 | GA 17-9 33-37-21 | L00226 =P C * | L00227 =P C | 001-099 |
| 0015 | 20 | GA 18-0 33-37-21 | L00226 =P C | L00227 =P C | 115-199 |
| 0016 | 20 | GA 1-11 33-37-21 | L00224 =G C | GD00705 AC.. E | 001-099 |
| 0016 | 20 | GA 3-0 33-37-21 | L00224 =G C | GD00705 AC.. E | 115-199 |
| 0017 | 20 | GA 1-10 33-37-21 | L00225 =G C | GD00708 AC.. E | 001-099 |
| 0017 | 20 | GA 3-0 33-37-21 | L00225 =G C | GD00708 AC.. E | 115-199 |
| 0018 | 20 | GA 1-10 33-37-21 | L00226 =G C | GD00713 AC.. E | 001-099 |
| 0018 | 20 | GA 3-0 33-37-21 | L00226 =G C | GD00713 AC.. E | 115-199 |
| 0019 | 20 | GA 2-2 33-37-21 | L00227 =G C | GD00715 AC.. E | 001-099 |
| 0019 | 20 | GA 2-0 33-37-21 | L00227 =G C | GD00715 AC.. E | 115-199 |
| 0020 | 18 | GA 22-6 33-37-21 | C04046 =L D | L00231 =P C * | 001-099 |
| 0020 | 18 | GA 40-0 33-37-21 | C04046 =L D | L00231 =P C * | 115-199 |
| 0021 | 20 | GA 20-1 33-37-21 | L00231 =P C * | L00230 =P C * | 001-099 |
| 0021 | 20 | GA 22-0 33-37-21 | L00231 =P C * | L00230 =P C * | 115-199 |
| 0022 | 20 | GA 23-4 33-37-21 | L00230 =P C * | L00229 =P C * | 001-099 |
| 0022 | 20 | GA 22-0 33-37-21 | L00230 =P C * | L00229 =P C * | 115-199 |
| 0023 | 20 | GA 23-9 33-37-21 | L00229 =P C * | L00228 =P C | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2660

Page 1

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2660
Page 2
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2662 | 286N2662 | | | E6 TO AFT CARGO BAY (continued) | | | | | | | | | | | |
| 0047 | 20 | | GA | | 3-0 | 52-35-11 | SM00002 | | | 9 | D02322 | 2 | | | 115-199 |
| 0048 | 20 | | GA | | 3-0 | 52-35-11 | SM00003 | | | 9 | D02322 | 3 | | | 115-199 |
| 0049 | 20 | | GA | | 31-0 | 25-51-21 | D02468 | 7 | | | SM00004 | | 9 | | 115-199 |
| 0050 | 20 | | GA | | 34-0 | 25-51-21 | D04748 | 1 | | | S10207 | 5 | C | | 115-199 |
| 0051 | 20 | | GA | | 5-0 | 25-51-21 | S10207 | 2 | C | | SM00004 | | 9 | | 115-199 |
| 0052 | 20 | | GA | | 33-0 | 25-51-21 | S10207 | 6 | C | | D41932P | 16 | | | 115-199 |
| 0053 | 20 | | GA | | 33-0 | 25-51-21 | S10207 | 4 | C | | D41932P | 17 | | | 115-199 |
| 0054 | 22 | | GA | | 7-2 | 52-35-11 | SP00184 | | | 9 | D41168J | 7 | | | 001-099 |
| 0054 | 22 | | GA | | 9-0 | 52-35-11 | SP00184 | | | 9 | D41168J | 7 | | | 115-199 |
| 0062 | 20 | | GA | | 8-0 | 25-51-21 | S10212 | NC | C | | GD00140 | DC.. | E | | 115-199 |
| B-BL | | | | | 0-0 | 25-51-21 | S10210 | BLU | | | GD00139 | DC.. | E | | 115-199 |
| B-RD | | | | | 0-0 | 25-51-21 | S10210 | RED | | | SP00202 | | 9 | | 115-199 |
| W2663 | 286N2663 | | | HF-L COMM, E4-3 TO STA 1685 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 121-0 | 23-11-11 | D42033P | 1 | | | D41733P | 1 | | | 001-099 |
| 0001 | 20 | | GA | | 38-0 | 23-11-11 | D41799P | 1 | | | D41733P | 1 | | | 115-199 |
| 0002 | 20 | | GA | | 121-0 | 23-11-11 | D42033P | 2 | | | D41733P | 2 | | | 001-099 |
| 0002 | 20 | | GA | | 38-0 | 23-11-11 | D41799P | 2 | | | D41733P | 2 | | | 115-199 |
| 0003 | 20 | | GA | | 121-0 | 23-11-11 | D42033P | 3 | | | D41733P | 3 | | | 001-099 |
| 0003 | 20 | | GA | | 38-0 | 23-11-11 | D41799P | 3 | | | D41733P | 3 | | | 115-199 |
| 0004 | 20 | | GA | | 121-0 | 23-11-11 | D42033P | 4 | | | D41733P | 4 | | | 001-099 |
| 0004 | 20 | | GA | | 38-0 | 23-11-11 | D41799P | 4 | | | D41733P | 4 | | | 115-199 |
| 0005 | 20 | | GA | | 121-0 | 23-11-11 | D42033P | 5 | | | D41733P | 5 | | | 001-099 |
| 0005 | 20 | | GA | | 38-0 | 23-11-11 | D41799P | 5 | | | D41733P | 5 | | | 115-199 |
| 0006 | 20 | | GA | | 121-0 | 23-11-11 | D42033P | 6 | | | D41733P | 6 | | | 001-099 |
| 0006 | 20 | | GA | | 38-0 | 23-11-11 | D41799P | 6 | | | D41733P | 6 | | | 115-199 |
| 0007 | 20 | | GA | | 121-0 | 23-11-11 | D42033P | 7 | | | D41733P | 7 | | | 001-099 |
| 0007 | 20 | | GA | | 38-0 | 23-11-11 | D41799P | 7 | | | D41733P | 7 | | | 115-199 |
| 0008 | 20 | | GA | | 121-0 | 23-11-11 | D42033P | 8 | | | D41733P | 8 | | | 001-099 |
| 0008 | 20 | | GA | | 38-0 | 23-11-11 | D41799P | 8 | | | D41733P | 8 | | | 115-199 |
| 0009 | 20 | | GA | | 121-0 | SPARE | D42033P | 9 | | | D41733P | 9 | | | 001-099 |
| 0009 | 20 | | GA | | 38-0 | SPARE | D41799P | 9 | | | D41733P | 9 | | | 115-199 |
| 0010 | 20 | | GA | | 121-0 | SPARE | D42033P | 10 | | | D41733P | 10 | | | 001-099 |
| 0010 | 20 | | GA | | 38-0 | SPARE | D41799P | 10 | | | D41733P | 10 | | | 115-199 |
| W2665 | 286N2665 | | | HF-R COMM, E3-2 TO STA 1685 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 126-0 | 23-11-21 | D42059P | 1 | | | D41735J | 1 | | | 001-099 |
| 0001 | 20 | | GA | | 41-0 | 23-11-21 | D41813P | 1 | | | D41735P | 1 | | | 115-199 |
| 0002 | 20 | | GA | | 126-0 | 23-11-21 | D42059P | 2 | | | D41735J | 2 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2660

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------|-------|----------|--|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2665 | 286N2665 | | | | | | HF-R COMM, E3-2 TO STA 1685 (continued) | | | | | | | | |
| 0002 | 20 | | GA | | 41-0 | 23-11-21 | D41813P | | | 2 | D41735P | | | 2 | 115-199 |
| 0003 | 20 | | GA | | 126-0 | 23-11-21 | D42059P | | | 3 | D41735J | | | 3 | 001-099 |
| 0003 | 20 | | GA | | 41-0 | 23-11-21 | D41813P | | | 3 | D41735P | | | 3 | 115-199 |
| 0004 | 20 | | GA | | 126-0 | 23-11-21 | D42059P | | | 4 | D41735J | | | 4 | 001-099 |
| 0004 | 20 | | GA | | 41-0 | 23-11-21 | D41813P | | | 4 | D41735P | | | 4 | 115-199 |
| 0005 | 20 | | GA | | 126-0 | 23-11-21 | D42059P | | | 5 | D41735J | | | 5 | 001-099 |
| 0005 | 20 | | GA | | 41-0 | 23-11-21 | D41813P | | | 5 | D41735P | | | 5 | 115-199 |
| 0006 | 20 | | GA | | 126-0 | 23-11-21 | D42059P | | | 6 | D41735J | | | 6 | 001-099 |
| 0006 | 20 | | GA | | 41-0 | 23-11-21 | D41813P | | | 6 | D41735P | | | 6 | 115-199 |
| 0007 | 20 | | GA | | 126-0 | 23-11-21 | D42059P | | | 7 | D41735J | | | 7 | 001-099 |
| 0007 | 20 | | GA | | 41-0 | 23-11-21 | D41813P | | | 7 | D41735P | | | 7 | 115-199 |
| 0008 | 20 | | GA | | 126-0 | 23-11-21 | D42059P | | | 8 | D41735J | | | 8 | 001-099 |
| 0008 | 20 | | GA | | 41-0 | 23-11-21 | D41813P | | | 8 | D41735P | | | 8 | 115-199 |
| 0009 | 20 | | GA | | 126-0 | SPARE | D42059P | | | 9 | D41735J | | | 9 | 001-099 |
| 0009 | 20 | | GA | | 41-0 | SPARE | D41813P | | | 9 | D41735P | | | 9 | 115-199 |
| 0010 | 20 | | GA | | 126-0 | SPARE | D42059P | | | 10 | D41735J | | | 10 | 001-099 |
| 0010 | 20 | | GA | | 41-0 | SPARE | D41813P | | | 10 | D41735P | | | 10 | 115-199 |
| W2667 | 286N2667 | | | | | | HF-L RF COAX, E4-3 TO AA1671 | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-11-11 | D42043P | | = C1 | | D40193P | | = C1 | | 001-099 |
| 001CO | | | | AA | 0-0 | 23-11-11 | D41807P | | = C1 | | D40193P | | = C1 | | 115-199 |
| 001CX | | | BS | AA | 116-0 | 23-11-11 | D42043P | | = A1 | | D40193P | | = A1 | | 001-099 |
| 001CX | | | BS | AA | 38-0 | 23-11-11 | D41807P | | = A1 | | D40193P | | = A1 | | 115-199 |
| W2669 | 286N2669 | | | | | | HF-R RF COAX, E3-2 TO AB1671 | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-11-21 | D42057P | | = C1 | | D40197P | | = C1 | | 001-099 |
| 001CO | | | | AA | 0-0 | 23-11-21 | D41805P | | = C1 | | D40197P | | = C1 | | 115-199 |
| 001CX | | | BS | AA | 116-0 | 23-11-21 | D42057P | | = A1 | | D40197P | | = A1 | | 001-099 |
| 001CX | | | BS | AA | 38-0 | 23-11-21 | D41805P | | = A1 | | D40197P | | = A1 | | 115-199 |

WIRE LIST

D280N032

91-21-11
Section W2660
Page 4 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2689 | 286N2689 | | | | PASSENGER ENT.L. SIDEWALL STA 625 TO L. SIDEWALL STA 753 L. | | | | | | | | | | | |
| 0001 | 20 | | GA | | 1-0 | 23-34-13 | D01413 | | D | | | SM00001 | | 9 | | 001-099 |
| 0002 | 20 | | GA | | 1-0 | 23-34-13 | D01413 | | E | | | SM00002 | | 9 | | 001-099 |
| 0003 | 20 | | GA | | 1-0 | 23-34-13 | SM00003 | | | 9 | | D01415 | D | | | 001-099 |
| 0004 | 20 | | GA | | 1-0 | 23-34-13 | SM00004 | | | 9 | | D01415 | E | | | 001-099 |
| 0005 | 22 | | GA | | 34-0 | 23-34-13 | D01413 | | F | | | D01415 | F | | | 001-099 |
| 2001B | 18 | | GB | A | 33-0 | 23-34-13 | SM00002 | | | 9 | | SM00004 | | 9 | | 001-099 |
| 2001R | 18 | | GB | A | 0-0 | 23-34-13 | SM00001 | | | 9 | | SM00003 | | 9 | | 001-099 |
| 2501B | 24 | | W9 | B | 34-0 | 23-34-13 | D01413 | | B | | | D01415 | B | | | 001-099 |
| 2501W | 24 | | W9 | B | 0-0 | 23-34-13 | D01413 | | A | | | D01415 | A | | | 001-099 |
| 2501Z | | | | B | 0-0 | 23-34-13 | D01413 | | C | | | D01415 | C | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2680

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2700 | 286N2700 | | | P6 TO E6, APU TRU AND APU BATT CHARGER | | | | | | | | | | | |
| 0004 | 18 | | GA | | 122-0 | 24-31-41 | D41082P | | 4 | | D40170P | | 4 | | 001-099 |
| 0004 | 18 | | GA | | 147-0 | 24-31-41 | D41082P | | 4 | | D40170P | | 4 | | 115-199 |
| 0005 | 18 | | GA | | 122-0 | 24-31-41 | D41082P | | 5 | | D40170P | | 5 | | 001-099 |
| 0005 | 18 | | GA | | 147-0 | 24-31-41 | D41082P | | 5 | | D40170P | | 5 | | 115-199 |
| 0006 | 18 | | GA | | 122-0 | 24-31-41 | D41082P | | 6 | | D40170P | | 6 | | 001-099 |
| 0006 | 18 | | GA | | 147-0 | 24-31-41 | D41082P | | 6 | | D40170P | | 6 | | 115-199 |
| 0007 | 22 | | GA | | 134-0 | SPARE | D40168P | | 1 | | D40170P | | 1 | | 001-099 |
| 0007 | 22 | | GA | | 151-0 | SPARE | D40168P | | 1 | | D40170P | | 1 | | 115-199 |
| 0008 | 20 | | GA | | 122-0 | 24-32-41 | D41082P | | 2 | | D40170P | | 2 | | 001-099 |
| 0008 | 20 | | GA | | 147-0 | 24-32-41 | D41082P | | 2 | | D40170P | | 2 | | 115-199 |
| 0009 | 20 | | GA | | 134-0 | SPARE | D40168P | | 3 | | D40170P | | 3 | | 001-099 |
| 0009 | 20 | | GA | | 151-0 | SPARE | D40168P | | 3 | | D40170P | | 3 | | 115-199 |
| 0010 | 18 | | GA | | 54-0 | 25-29-11 | D40168P | | 4 | | D00882 | =P | D | | 001-099 |
| 0010 | 18 | | GA | | 24-0 | 25-29-11 | D40168P | | 4 | | D00882 | =P | D | | 115-199 |
| 0011 | 18 | | GA | | 7-0 | 25-29-11 | D00882 | =N | D | | GD01082 | AC.. | E | | ALL |
| 0012 | 18 | | GA | | 7-0 | 25-29-11 | D00882 | =G | D | | GD02608 | ST.. | E | | ALL |
| 0013 | 18 | | GA | | 121-0 | 25-29-11 | D40168P | | 5 | | D00884 | =P | D | | 001-099 |
| 0013 | 18 | | GA | | 114-0 | 25-29-11 | D40168P | | 5 | | D00884 | =P | D | | 115-199 |
| 0014 | 18 | | GA | | 6-0 | 25-29-11 | D00884 | =N | D | | GD01084 | AC.. | E | | 001-099 |
| 0014 | 18 | | GA | | 5-0 | 25-29-11 | D00884 | =N | D | | GD01084 | AC.. | E | | 115-199 |
| 0015 | 18 | | GA | | 6-0 | 25-29-11 | D00884 | =G | D | | GD02530 | ST.. | E | | 001-099 |
| 0015 | 18 | | GA | | 5-0 | 25-29-11 | D00884 | =G | D | | GD02530 | ST.. | E | | 115-199 |
| 0016 | 08 | 43 | | | 121-0 | 24-32-41 | TB5032 | | 13 | BS | K10010 | A1 | BS | | 001-099 |
| 0016 | 08 | 43 | | | 145-8 | 24-32-41 | TB5032 | | 13 | BS | K10010 | A1 | BS | | 115-199 |
| 0017 | 08 | 43 | | | 121-0 | 24-32-41 | TB5032 | | 14 | BS | K10010 | B1 | BS | | 001-099 |
| 0017 | 08 | 43 | | | 145-8 | 24-32-41 | TB5032 | | 14 | BS | K10010 | B1 | BS | | 115-199 |
| 0018 | 08 | 43 | | | 121-0 | 24-32-41 | TB5032 | | 15 | BS | K10010 | C1 | BS | | 001-099 |
| 0018 | 08 | 43 | | | 145-8 | 24-32-41 | TB5032 | | 15 | BS | K10010 | C1 | BS | | 115-199 |
| 0022 | 24 | | GK | | 122-0 | SPARE | D40170P | | 12 | | D41082P | | 1 | | 001-099 |
| 0023 | 24 | | GK | | 122-0 | SPARE | D40170P | | 13 | | D41082P | | 3 | | 001-099 |
| 0601 | 20 | | GA | | 134-0 | SPARE | D40168P | | 2 | | D40170P | | 7 | | 001-099 |
| 0601 | 20 | | GA | | 151-0 | SPARE | D40168P | | 2 | | D40170P | | 7 | | 115-199 |
| 0602 | 20 | | GA | | 134-0 | SPARE | D40168P | | 6 | | D40170P | | 8 | | 001-099 |
| 0602 | 20 | | GA | | 151-0 | SPARE | D40168P | | 6 | | D40170P | | 8 | | 115-199 |
| 0603 | 20 | | GA | | 122-0 | SPARE | D41082P | | 7 | | D40170P | | 9 | | 001-099 |
| 0603 | 20 | | GA | | 147-0 | SPARE | D41082P | | 7 | | D40170P | | 9 | | 115-199 |
| 0604 | 20 | | GA | | 134-0 | SPARE | D40168P | | 8 | | D40170P | | 10 | | 001-099 |
| 0604 | 20 | | GA | | 151-0 | SPARE | D40168P | | 8 | | D40170P | | 10 | | 115-199 |
| 0605 | 20 | | GA | | 134-0 | SPARE | D40168P | | 9 | | D40170P | | 11 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2700

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|---------|------|-------------|--------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W2700 | 286N2700 | | | | P6 TO E6, APU TRU AND APU BATT CHARGER (continued) | | | | | | | | | | | |
| 0605 | 20 | | GA | | 151-0 | SPARE | | D40168P | 9 | | | D40170P | 11 | | | 115-199 |
| W2702 | 286N2702 | | | | P6 TO E6 STBY PWR - EXTENDED | | | | | | | | | | | |
| 0001 | *2 | | 43 | | 123-6 | 24-33-12 | | TB5017 | = 1 | H* | | M10496 | A2 | BU | | 001-099 |
| W2706 | 286N2706 | | | | LEFT STA 820 TO E-6 RACK - AIR CONDITIONING SYSTEM. | | | | | | | | | | | |
| 0003 | 22 | | GA | | 103-0 | 21-51-13 | | D41845P | 37 | | | D40628P | 1 | | | 115-199 |
| 0004 | 22 | | GA | | 103-0 | 21-51-13 | | D41845P | 38 | | | D40628P | 2 | | | 115-199 |
| 0005 | 22 | | GA | | 103-0 | 21-51-13 | | D41845P | 3 | | | D40628P | 3 | | | 115-199 |
| 0006 | 22 | | GA | | 103-0 | 21-51-13 | | D41845P | 4 | | | D40628P | 4 | | | 115-199 |
| 0007 | 24 | | GK | | 102-0 | SPARE | | D42188P | 40 | | | D40628P | 40 | | | 115-199 |
| 0008 | 24 | | GK | | 103-0 | SPARE | | D41845P | 41 | | | D40628P | 41 | | | 115-199 |
| 0009 | 24 | | GK | | 101-0 | SPARE | | D42180P | 45 | | | D40628P | 45 | | | 115-199 |
| 0010 | 24 | | GK | | 103-0 | SPARE | | D41845P | 42 | | | D40630P | 42 | | | 115-199 |
| 0011 | 24 | | GK | | 101-0 | SPARE | | D42180P | 48 | | | D40630P | 48 | | | 115-199 |
| 0012 | 24 | | GK | | 104-0 | SPARE | | D41845P | 43 | | | D40632P | 43 | | | 115-199 |
| 0013 | 24 | | GK | | 104-0 | SPARE | | D41845P | 44 | | | D40632P | 44 | | | 115-199 |
| 0014 | 24 | | GK | | 9-0 | SPARE | | D41845P | 47 | | | D42188P | 47 | | | 115-199 |
| 0015 | 24 | | GK | | 9-0 | SPARE | | D41845P | 48 | | | D42188P | 48 | | | 115-199 |
| 0016 | 24 | | GK | | 9-0 | SPARE | | D41845P | 49 | | | D42180P | 49 | | | 115-199 |
| 0017 | 24 | | GK | | 9-0 | SPARE | | D41845P | 50 | | | D42180P | 50 | | | 115-199 |
| 0030 | 22 | | GA | | 103-0 | 21-51-13 | | D41845P | 39 | | | D40628P | 5 | | | 115-199 |
| 0031 | 22 | | GA | | 103-0 | 21-51-13 | | D41845P | 40 | | | D40628P | 6 | | | 115-199 |
| 0050 | 24 | | GK | | 103-0 | 21-51-14 | | D40630P | 1 | | | D41845P | 5 | | | 115-199 |
| 0066 | 24 | | GK | | 10-0 | 21-51-12 | | D42182P | 8 | | | D41845P | 8 | | | 115-199 |
| 0067 | 24 | | GK | | 10-0 | 21-51-12 | | D42182P | 7 | | | D41845P | 7 | | | 115-199 |
| 0068 | 24 | | GK | | 10-0 | 21-51-12 | | D42182P | 6 | | | D41845P | 6 | | | 115-199 |
| 0069 | 24 | | GK | | 10-0 | 21-51-12 | | D42182P | 5 | | | D41845P | 24 | | | 115-199 |
| 0070 | 24 | | GK | | 10-0 | 21-51-12 | | D42182P | 4 | | | D41845P | 23 | | | 115-199 |
| 0071 | 24 | | GK | | 10-0 | 21-51-12 | | D42182P | 3 | | | D41845P | 20 | | | 115-199 |
| 0085 | 24 | | GK | | 103-0 | 21-51-13 | | D41845P | 12 | | | D40630P | 2 | | | 115-199 |
| 0091 | 24 | | GK | | 103-0 | 21-51-13 | | D40630P | 3 | | | D41845P | 13 | | | 115-199 |
| 0092 | 24 | | GK | | 103-0 | 21-51-13 | | D40630P | 4 | | | D41845P | 14 | | | 115-199 |
| 0093 | 24 | | GK | | 103-0 | 21-51-13 | | D40630P | 5 | | | D41845P | 15 | | | 115-199 |
| 0094 | 24 | | GK | | 103-0 | 21-51-13 | | D40630P | 6 | | | D41845P | 16 | | | 115-199 |
| 0095 | 24 | | GK | | 103-0 | 21-51-13 | | D40630P | 7 | | | D41845P | 17 | | | 115-199 |
| 0096 | 24 | | GK | | 103-0 | 21-51-13 | | D40630P | 8 | | | D41845P | 18 | | | 115-199 |
| 0099 | 24 | | GK | | 103-0 | 21-51-13 | | D40630P | 9 | | | D41845P | 34 | | | 115-199 |
| 0126 | 24 | | GK | | 103-0 | 21-51-11 | | D40630P | 10 | | | D41845P | 51 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2700

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2706 | 286N2706 | | | LEFT STA 820 TO E-6 RACK - AIR CONDITIONING SYSTEM. (continued) | | | | | | | | | | | |
| 0134 | 24 | | GK | | 10-0 | 21-51-12 | D42182P | | 9 | | D41845P | | 9 | | 115-199 |
| 0135 | 24 | | GK | | 103-0 | 21-51-12 | D41845P | | 53 | | D40630P | | 11 | | 115-199 |
| 0160 | 24 | | GK | | 103-0 | 21-51-15 | D41845P | | 27 | | D40630P | | 12 | | 115-199 |
| 0161 | 24 | | GK | | 10-0 | 21-51-15 | D41845P | | 28 | | D42182P | | 42 | | 115-199 |
| 0162 | 24 | | GK | | 103-0 | 21-51-15 | D40630P | | 13 | | D41845P | | 29 | | 115-199 |
| 0163 | 24 | | GK | | 103-0 | 21-51-15 | D42182P | | 43 | | D40632P | | 1 | | 115-199 |
| 0164 | 24 | | GK | | 10-0 | 21-51-15 | D41845P | | 31 | | D42182P | | 53 | | 115-199 |
| 0185 | 22 | | GA | | 102-0 | 32-42-11 | D40632P | | 2 | | D42180P | | 36 | | 115-199 |
| 0211 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 3 | | D42180P | | 20 | | 115-199 |
| 0212 | 22 | | GA | | 101-0 | 32-42-11 | D40630P | | 14 | | D42180P | | 13 | | 115-199 |
| 0213 | 22 | | GA | | 101-0 | 32-42-11 | D40630P | | 15 | | D42180P | | 18 | | 115-199 |
| 0214 | 22 | | GA | | 101-0 | 32-42-11 | D40630P | | 16 | | D42180P | | 19 | | 115-199 |
| 0215 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 4 | | D42180P | | 1 | | 115-199 |
| 0216 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 5 | | D42180P | | 2 | | 115-199 |
| 0217 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 6 | | D42180P | | 3 | | 115-199 |
| 0218 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 7 | | D42180P | | 4 | | 115-199 |
| 0219 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 8 | | D42180P | | 5 | | 115-199 |
| 0220 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 9 | | D42180P | | 6 | | 115-199 |
| 0221 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 10 | | D42180P | | 7 | | 115-199 |
| 0222 | 24 | | GK | | 102-0 | 32-46-11 | D40632P | | 11 | | D42180P | | 8 | | 115-199 |
| 0223 | 24 | | GK | | 102-0 | 32-41-11 | D40632P | | 12 | | D42180P | | 21 | | 115-199 |
| 0224 | 24 | | GK | | 102-0 | SPARE | D40632P | | 13 | | D42180P | | 22 | | 115-199 |
| 0225 | 24 | | GK | | 102-0 | SPARE | D40632P | | 14 | | D42180P | | 23 | | 115-199 |
| 0226 | 24 | | GK | | 102-0 | SPARE | D40632P | | 15 | | D42180P | | 24 | | 115-199 |
| 0227 | 24 | | GK | | 102-0 | SPARE | D40632P | | 16 | | D42180P | | 25 | | 115-199 |
| 0228 | 24 | | GK | | 102-0 | SPARE | D40632P | | 17 | | D42180P | | 26 | | 115-199 |
| 0229 | 24 | | GK | | 102-0 | SPARE | D40632P | | 18 | | D42180P | | 27 | | 115-199 |
| 0230 | 24 | | GK | | 102-0 | SPARE | D40632P | | 19 | | D42180P | | 28 | | 115-199 |
| 0232 | 22 | | GA | | 101-0 | 32-42-11 | D40630P | | 17 | | D42180P | | 16 | | 115-199 |
| 0237 | 22 | | GA | | 101-0 | 32-42-12 | D40630P | | 19 | | D42180P | | 15 | | 115-199 |
| 0238 | 22 | | GA | | 101-0 | 32-42-12 | D40630P | | 20 | | D42180P | | 17 | | 115-199 |
| 0239 | 24 | | GK | | 102-0 | 21-61-51 | D42188P | | 3 | | D40632P | | 20 | | 115-199 |
| 0242 | 24 | | GK | | 105-0 | 21-58-11 | D04222 | | 2 | | D40630P | | 21 | | 115-199 |
| 0243 | 20 | | GA | | 4-0 | 21-58-11 | D04222 | | 3 | | GD02610 | DC.. | 2 | | 115-199 |
| 0244 | 20 | | GA | | 4-0 | 21-58-11 | D04222 | | 4 | | GD02610 | ST.. | 2 | | 115-199 |
| 0245 | 24 | | GK | | 105-0 | 21-58-11 | D04222 | | 5 | | D40630P | | 22 | | 115-199 |
| 0246 | 20 | | GA | | 105-0 | 21-58-11 | D04222 | | 1 | | D40630P | | 23 | | 115-199 |
| 0250 | 22 | | GA | | 107-0 | 21-58-24 | D04214 | | 3 | | D40630P | | 25 | | 115-199 |
| 0251 | 22 | | GA | | 107-0 | 21-58-24 | D04214 | | 2 | | D40630P | | 26 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2700

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2706 | 286N2706 | | | LEFT STA 820 TO E-6 RACK - AIR CONDITIONING SYSTEM. (continued) | | | | | | | | | | | |
| 0252 | 22 | GA | | | 107-0 | 21-58-24 | D04214 | | 1 | | D40630P | 27 | | | 115-199 |
| 0253 | 22 | GA | | | 107-0 | 21-58-24 | D04214 | | 5 | | D40630P | 28 | | | 115-199 |
| 0254 | 22 | GA | | | 107-0 | 21-58-24 | D04214 | | 6 | | D40630P | 29 | | | 115-199 |
| 0255 | 20 | GA | | | 5-0 | 21-58-24 | D04214 | | 7 | | GD02610 | ST.. | 2 | | 115-199 |
| 0257 | 20 | GA | | | 102-0 | 21-51-12 | D40630P | | 30 | | D42182P | 1 | | | 115-199 |
| 0258 | 24 | GK | | | 10-0 | SPARE | D41845P | | 36 | | D42182P | 2 | | | 115-199 |
| 0259 | 24 | GK | | | 102-0 | 21-61-51 | D40630P | | 31 | | D42182P | 52 | | | 115-199 |
| 0265 | 24 | GK | | | 9-0 | 21-51-11 | D41845P | | 52 | | D42180P | 30 | | | 115-199 |
| 0266 | 24 | GK | | | 9-0 | 21-51-14 | D42182P | | 12 | | D41845P | 35 | | | 115-199 |
| 0269 | 22 | GA | | | 101-0 | 32-42-11 | D40630P | | 41 | | D42180P | 9 | | | 115-199 |
| 2000B | 24 | GL | AC | | 101-0 | SPARE | D42180P | | 46 | | D40628P | 46 | | | 115-199 |
| 2000R | 24 | GL | AC | | 0-0 | SPARE | D42180P | | 47 | | D40628P | 47 | | | 115-199 |
| 2002B | 24 | GL | AD | | 104-0 | SPARE | D41845P | | 45 | | D40632P | 45 | | | 115-199 |
| 2002R | 24 | GL | AD | | 0-0 | SPARE | D41845P | | 46 | | D40632P | 46 | | | 115-199 |
| 2012B | 24 | GL | BA | | 102-0 | 21-51-14 | D42182P | | 49 | | D40628P | 7 | | | 115-199 |
| 2012R | 24 | GL | BA | | 0-0 | 21-51-14 | D42182P | | 48 | | D40628P | 8 | | | 115-199 |
| 2013B | 24 | GL | BC | | 10-0 | 21-51-14 | D42182P | | 51 | | D41845P | 2 | | | 115-199 |
| 2013R | 24 | GL | BC | | 0-0 | 21-51-14 | D42182P | | 50 | | D41845P | 1 | | | 115-199 |
| 2014B | 24 | GL | BD | | 10-0 | 21-51-14 | D42182P | | 40 | | D41845P | 21 | | | 115-199 |
| 2014R | 24 | GL | BD | | 0-0 | 21-51-14 | D42182P | | 41 | | D41845P | 22 | | | 115-199 |
| 2015B | 24 | GL | BE | | 103-0 | 21-51-14 | D41845P | | 26 | | D40628P | 9 | | | 115-199 |
| 2015R | 24 | GL | BE | | 0-0 | 21-51-14 | D41845P | | 25 | | D40628P | 10 | | | 115-199 |
| 2029B | 24 | GL | AA | | 102-0 | 21-51-14 | D42182P | | 47 | | D40628P | 11 | | | 115-199 |
| 2029R | 24 | GL | AA | | 0-0 | 21-51-14 | D42182P | | 46 | | D40628P | 12 | | | 115-199 |
| 2040B | 24 | GL | AS | | 10-0 | 21-51-12 | D42182P | | 11 | | D41845P | 11 | | | 115-199 |
| 2040R | 24 | GL | AS | | 0-0 | 21-51-12 | D42182P | | 10 | | D41845P | 10 | | | 115-199 |
| 2041B | 24 | GL | AT | | 103-0 | 21-51-12 | D41845P | | 33 | | D40628P | 13 | | | 115-199 |
| 2041R | 24 | GL | AT | | 0-0 | 21-51-12 | D41845P | | 32 | | D40628P | 14 | | | 115-199 |
| 2042B | 24 | GL | BG | | 102-0 | 21-51-15 | D42182P | | 44 | | D40628P | 15 | | | 115-199 |
| 2042R | 24 | GL | BG | | 0-0 | 21-51-15 | D42182P | | 45 | | D40628P | 16 | | | 115-199 |
| 2049B | 24 | GL | CB | | 102-0 | 21-51-12 | D42182P | | 15 | | D40630P | 33 | | | 115-199 |
| 2049R | 24 | GL | CB | | 0-0 | 21-51-12 | D42182P | | 16 | | D40630P | 34 | | | 115-199 |
| 2050B | 24 | GL | BR | | 101-0 | 21-61-51 | D40630P | | 35 | | D42188P | 2 | | | 115-199 |
| 2050R | 24 | GL | BR | | 0-0 | 21-61-51 | D40630P | | 36 | | D42188P | 1 | | | 115-199 |
| 2051B | 24 | GL | CA | | 102-0 | 21-51-12 | D40628P | | 17 | | D42182P | 21 | | | 115-199 |
| 2051R | 24 | GL | CA | | 0-0 | 21-51-12 | D40628P | | 18 | | D42182P | 20 | | | 115-199 |
| 2052B | 24 | GL | CD | | 128-0 | 21-61-21 | D02568 | | 2 | | D42188P | 22 | | | 115-199 |
| 2052R | 24 | GL | CD | | 0-0 | 21-61-21 | D02568 | | 1 | | D42188P | 21 | | | 115-199 |
| 2053B | 24 | GL | CE | | 128-0 | 21-61-21 | D02568 | | 4 | | D42188P | 24 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2700

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2706 | 286N2706 | | | LEFT STA 820 TO E-6 RACK - AIR CONDITIONING SYSTEM. (continued) | | | | | | | | | | | |
| 2053R | 24 | GL | CE | | 0-0 | 21-61-21 | D02568 | | | | D42188P | 23 | | | 115-199 |
| 2054B | 24 | GL | DC | | 103-0 | 21-51-12 | D42182P | | | | D40632P | 21 | | | 115-199 |
| 2054R | 24 | GL | DC | | 0-0 | 21-51-12 | D42182P | | | | D40632P | 22 | | | 115-199 |
| 2055B | 24 | GL | DE | | 7-0 | 21-61-51 | D42188P | | | | D42180P | 32 | | | 115-199 |
| 2055R | 24 | GL | DE | | 0-0 | 21-61-51 | D42188P | | | | D42180P | 31 | | | 115-199 |
| 3001B | 24 | GM | AU | | 102-0 | 21-51-12 | D42182P | | | | D40628P | 19 | | | 115-199 |
| 3001R | 24 | GM | AU | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 20 | | | 115-199 |
| 3001Y | 24 | GM | AU | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 21 | | | 115-199 |
| 3002B | 24 | GM | AV | | 102-0 | 21-51-12 | D42182P | | | | D40628P | 22 | | | 115-199 |
| 3002R | 24 | GM | AV | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 23 | | | 115-199 |
| 3002Y | 24 | GM | AV | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 24 | | | 115-199 |
| 3003B | 24 | GM | AW | | 102-0 | 21-51-12 | D42182P | | | | D40628P | 25 | | | 115-199 |
| 3003R | 24 | GM | AW | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 26 | | | 115-199 |
| 3003Y | 24 | GM | AW | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 27 | | | 115-199 |
| 3004B | 24 | GM | AX | | 102-0 | 21-51-12 | D42182P | | | | D40628P | 28 | | | 115-199 |
| 3004R | 24 | GM | AX | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 29 | | | 115-199 |
| 3004Y | 24 | GM | AX | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 30 | | | 115-199 |
| 3005B | 24 | GM | AY | | 102-0 | 21-51-12 | D42182P | | | | D40628P | 31 | | | 115-199 |
| 3005R | 24 | GM | AY | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 32 | | | 115-199 |
| 3005Y | 24 | GM | AY | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 33 | | | 115-199 |
| 3006B | 24 | GM | AZ | | 102-0 | 21-51-12 | D42182P | | | | D40628P | 34 | | | 115-199 |
| 3006R | 24 | GM | AZ | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 35 | | | 115-199 |
| 3006Y | 24 | GM | AZ | | 0-0 | 21-51-12 | D42182P | | | | D40628P | 36 | | | 115-199 |
| 3009B | 24 | GM | BB | | 102-0 | 21-51-12 | D40628P | | | | D42182P | 19 | | | 115-199 |
| 3009R | 24 | GM | BB | | 0-0 | 21-51-12 | D40628P | | | | D42182P | 17 | | | 115-199 |
| 3009Y | 24 | GM | BB | | 0-0 | 21-51-12 | D40628P | | | | D42182P | 18 | | | 115-199 |
| 5001B | 22 | GU | CC | | 101-0 | 32-42-11 | D40630P | | | | D42180P | 11 | | | 115-199 |
| 5001R | 22 | GU | CC | | 0-0 | 32-42-11 | D40630P | | | | D42180P | 10 | | | 115-199 |
| 5001Z | | | CC | | 0-0 | 32-42-11 | D40630P | | | | D42180P | 12 | | | 115-199 |

WIRE LIST

D280N032

91-21-11
Section W2700
Page 5 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2710 | 286N2710 | | | | JUMPER BUNDLE, AFT SMOKE DETECTOR 1 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 1-5 | 26-16-11 | | D41266P | | | | D04406 | 4 | | | 001-099 |
| 0002 | 20 | | GA | | 1-5 | 26-16-11 | | D41266P | 12 | | | D04406 | 12 | | | 001-099 |
| 0003 | 20 | | GA | | 1-5 | 26-16-11 | | D41266P | 11 | | | D04406 | 11 | | | 001-099 |
| 0004 | 20 | | GA | | 1-5 | 26-16-11 | | D41266P | 5 | | | D04406 | 5 | | | 001-099 |
| 0005 | 20 | | GA | | 1-5 | 26-16-11 | | D41266P | 9 | | | D04406 | 9 | | | 001-099 |
| W2712 | 286N2712 | | | | JUMPER BUNDLE, AFT BLOWER 1 | | | | | | | | | | | |
| 0417 | 22 | | GA | | 1-0 | 26-16-21 | | D41262P | 1 | | | D04428 | 1 | | | 001-099 |
| 0429 | 20 | | GA | | 1-0 | 26-16-21 | | D41262P | 2 | | | D04428 | 2 | | | 001-099 |
| 0430 | 20 | | GA | | 1-0 | 26-16-21 | | D41262P | 3 | | | D04428 | 3 | | | 001-099 |
| W2716 | 286N2716 | | | | RIGHT STA 820 TO E-6 RACK - AIR COND. SYSTEM. | | | | | | | | | | | |
| 0001 | 24 | | GK | | 7-0 | 21-51-22 | | D42196P | 1 | | | D41855P | 1 | | | 115-199 |
| 0002 | 24 | | GK | | 7-0 | 21-51-22 | | D42196P | 2 | | | D41855P | 2 | | | 115-199 |
| 0003 | 24 | | GK | | 7-0 | 21-51-22 | | D42196P | 3 | | | D41855P | 3 | | | 115-199 |
| 0004 | 24 | | GK | | 7-0 | 21-51-22 | | D42196P | 4 | | | D41855P | 4 | | | 115-199 |
| 0005 | 24 | | GK | | 7-0 | 21-51-22 | | D42196P | 5 | | | D41855P | 5 | | | 115-199 |
| 0006 | 24 | | GK | | 7-0 | 21-51-22 | | D42196P | 6 | | | D41855P | 6 | | | 115-199 |
| 0007 | 24 | | GK | | 7-0 | 21-51-22 | | D41855P | 7 | | | D42196P | 7 | | | 115-199 |
| 0008 | 24 | | GK | | 107-0 | SPARE | | D41638P | 46 | | | D41855P | 46 | | | 115-199 |
| 0009 | 24 | | GK | | 107-0 | SPARE | | D41638P | 47 | | | D41855P | 47 | | | 115-199 |
| 0010 | 24 | | GK | | 106-0 | SPARE | | D41642P | 48 | | | D41855P | 48 | | | 115-199 |
| 0011 | 24 | | GK | | 106-0 | SPARE | | D41642P | 49 | | | D41855P | 49 | | | 115-199 |
| 0012 | 24 | | GK | | 104-0 | SPARE | | D41642P | 43 | | | D42184P | 23 | | | 115-199 |
| 0013 | 24 | | GK | | 104-0 | SPARE | | D41642P | 44 | | | D42184P | 24 | | | 115-199 |
| 0014 | 24 | | GK | | 105-0 | SPARE | | D41638P | 48 | | | D42190P | 48 | | | 115-199 |
| 0015 | 24 | | GK | | 105-0 | SPARE | | D41638P | 49 | | | D42190P | 49 | | | 115-199 |
| 0016 | 24 | | GK | | 104-0 | SPARE | | D41642P | 38 | | | D42190P | 34 | | | 115-199 |
| 0017 | 24 | | GK | | 104-0 | SPARE | | D41642P | 41 | | | D42190P | 35 | | | 115-199 |
| 0018 | 24 | | GK | | 8-0 | SPARE | | D41855P | 23 | | | D42190P | 41 | | | 115-199 |
| 0019 | 24 | | GK | | 8-0 | SPARE | | D41855P | 25 | | | D42190P | 42 | | | 115-199 |
| 0020 | 24 | | GK | | 8-0 | SPARE | | D41855P | 38 | | | D42184P | 39 | | | 115-199 |
| 0021 | 24 | | GK | | 8-0 | SPARE | | D41855P | 44 | | | D42184P | 44 | | | 115-199 |
| 0022 | 24 | | GK | | 6-0 | SPARE | | D42190P | 12 | | | D42184P | 45 | | | 115-199 |
| 0023 | 22 | | GA | | 6-0 | SPARE | | D42190P | 11 | | | D42184P | 46 | | | 115-199 |
| 0037 | 24 | | GK | | 18-0 | 21-61-31 | | D02578 | 1 | | | D41640P | 1 | | | 115-199 |
| 0038 | 20 | | GA | | 2-0 | 21-61-31 | | D02578 | 2 | | | GD01489 | DC.. | E | | 115-199 |
| 0039 | 24 | | GK | | 18-0 | 21-61-21 | | D02564 | 1 | | | D41640P | 2 | | | 115-199 |
| 0040 | 20 | | GA | | 2-0 | 21-61-21 | | D02564 | 2 | | | GD01490 | DC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2710

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2716 | 286N2716 | | | RIGHT STA 820 TO E-6 RACK - AIR COND. SYSTEM. (continued) | | | | | | | | | | | |
| 0047 | 24 | | GK | | 106-0 | 21-51-23 | D41642P | | 1 | | D41855P | 17 | | | 115-199 |
| 0048 | 24 | | GK | | 106-0 | 21-51-23 | D41642P | | 2 | | D41855P | 39 | | | 115-199 |
| 0049 | 24 | | GK | | 106-0 | 21-51-23 | D41642P | | 3 | | D41855P | 40 | | | 115-199 |
| 0050 | 24 | | GK | | 106-0 | 21-51-23 | D41642P | | 4 | | D41855P | 41 | | | 115-199 |
| 0051 | 24 | | GK | | 106-0 | 21-51-23 | D41642P | | 5 | | D41855P | 42 | | | 115-199 |
| 0052 | 24 | | GK | | 106-0 | 21-51-23 | D41642P | | 6 | | D41855P | 43 | | | 115-199 |
| 0060 | 22 | | GA | | 107-0 | 21-51-23 | D41855P | | 32 | | D41638P | 1 | | | 115-199 |
| 0061 | 22 | | GA | | 106-0 | 21-51-23 | D41855P | | 33 | | D41638P | 2 | | | 115-199 |
| 0062 | 22 | | GA | | 106-0 | 21-51-23 | D41855P | | 34 | | D41638P | 3 | | | 115-199 |
| 0063 | 22 | | GA | | 106-0 | 21-51-23 | D41855P | | 35 | | D41638P | 4 | | | 115-199 |
| 0064 | 22 | | GA | | 106-0 | 21-51-23 | D41855P | | 36 | | D41638P | 5 | | | 115-199 |
| 0065 | 22 | | GA | | 106-0 | 21-51-23 | D41855P | | 37 | | D41638P | 6 | | | 115-199 |
| 0066 | 24 | | GK | | 8-0 | 21-51-24 | D42186P | | 1 | | D41855P | 29 | | | 115-199 |
| 0067 | 24 | | GK | | 106-0 | 21-51-24 | D41855P | | 28 | | D41642P | 7 | | | 115-199 |
| 0093 | 20 | | GA | | 105-0 | 28-25-11 | D41640P | | 3 | | D41855P | 51 | | | 115-199 |
| 0104 | 24 | | GK | | 106-0 | 21-51-22 | D41640P | | 4 | | D41855P | 45 | | | 115-199 |
| 0119 | 24 | | GK | | 2-0 | 21-65-12 | D04650 | | B | | SM00011 | | 9 | | 115-199 |
| 0120 | 24 | | GK | | 2-0 | 21-65-12 | D04652 | | B | | SM00012 | | 9 | | 115-199 |
| 0133 | 20 | | GA | | 2-0 | 21-65-12 | GD01490 | DC.. | E | | SM00011 | | 9 | | 115-199 |
| 0134 | 20 | | GA | | 2-0 | 21-65-12 | GD01489 | DC.. | E | | SM00012 | | 9 | | 115-199 |
| 0166 | 24 | | GK | | 106-0 | 21-51-23 | D41642P | | 8 | | D41855P | 16 | | | 115-199 |
| 0167 | 24 | | GK | | 106-0 | 21-51-25 | D41855P | | 21 | | D41642P | 9 | | | 115-199 |
| 0168 | 24 | | GK | | 8-0 | 21-51-25 | D41855P | | 22 | | D42196P | 36 | | | 115-199 |
| 0169 | 24 | | GK | | 106-0 | 21-51-25 | D41855P | | 24 | | D41642P | 10 | | | 115-199 |
| 0170 | 24 | | GK | | 104-0 | 21-51-25 | D42196P | | 37 | | D41642P | 11 | | | 115-199 |
| 0171 | 24 | | GK | | 7-0 | 21-51-25 | D41855P | | 26 | | D42196P | 35 | | | 115-199 |
| 0174 | 24 | | GK | | 104-0 | 21-61-11 | D42186P | | 11 | | D41640P | 5 | | | 115-199 |
| 0175 | 24 | | GK | | 104-0 | 21-61-11 | D42186P | | 12 | | D41640P | 6 | | | 115-199 |
| 0176 | 24 | | GK | | 104-0 | 21-61-11 | D42186P | | 13 | | D41640P | 7 | | | 115-199 |
| 0177 | 24 | | GK | | 104-0 | 21-61-11 | D42186P | | 14 | | D41640P | 8 | | | 115-199 |
| 0178 | 24 | | GK | | 104-0 | 21-61-11 | D42186P | | 15 | | D41640P | 9 | | | 115-199 |
| 0193 | 24 | | GK | | 104-0 | 21-61-21 | D42186P | | 26 | | D41640P | 10 | | | 115-199 |
| 0194 | 24 | | GK | | 104-0 | 21-61-21 | D42186P | | 27 | | D41640P | 11 | | | 115-199 |
| 0195 | 24 | | GK | | 104-0 | 21-61-21 | D42186P | | 28 | | D41640P | 12 | | | 115-199 |
| 0196 | 24 | | GK | | 104-0 | 21-61-21 | D42186P | | 29 | | D41640P | 13 | | | 115-199 |
| 0197 | 24 | | GK | | 104-0 | 21-61-21 | D42186P | | 30 | | D41640P | 14 | | | 115-199 |
| 0201 | 24 | | GK | | 104-0 | 21-61-31 | D42186P | | 43 | | D41640P | 15 | | | 115-199 |
| 0202 | 24 | | GK | | 104-0 | 21-61-31 | D42186P | | 44 | | D41640P | 16 | | | 115-199 |
| 0203 | 24 | | GK | | 104-0 | 21-61-31 | D42186P | | 45 | | D41640P | 17 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2710

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|---|---------|----------|---------|------|--------|-------|------|------|---------|-------------|---|---------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W2716 | 286N2716 | | | RIGHT STA 820 TO E-6 RACK - AIR COND. SYSTEM. (continued) | | | | | | | | | | | | |
| 0204 | 24 | | GK | | 104-0 | 21-61-31 | D42186P | | 46 | | | | D41640P | 18 | | 115-199 |
| 0210 | 24 | | GK | | 104-0 | 21-61-31 | D42186P | | 42 | | | | D41640P | 19 | | 115-199 |
| 0218 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 27 | | | | D41642P | 12 | | 115-199 |
| 0219 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 35 | | | | D41642P | 13 | | 115-199 |
| 0220 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 28 | | | | D41642P | 14 | | 115-199 |
| 0221 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 29 | | | | D41642P | 15 | | 115-199 |
| 0222 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 30 | | | | D41642P | 16 | | 115-199 |
| 0223 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 38 | | | | D41642P | 17 | | 115-199 |
| 0224 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 37 | | | | D41642P | 18 | | 115-199 |
| 0225 | 22 | | GA | | 106-0 | 52-35-11 | D41640P | | 20 | | | | D41855P | 13 | | 115-199 |
| 0226 | 22 | | GA | | 106-0 | 52-35-11 | D41640P | | 21 | | | | D41855P | 27 | | 115-199 |
| 0227 | 22 | | GA | | 131-0 | 52-35-11 | D41640P | | 22 | | | | SP01054 | | 9 | 115-199 |
| 0228 | 22 | | GA | | 14-0 | 52-35-11 | SP01054 | | | 9 | | | S10181 | 5 | C | 115-199 |
| 0229 | 22 | | GA | | 14-0 | 52-35-11 | SP01054 | | | 9 | | | S10181 | 2 | C | 115-199 |
| 0230 | 22 | | GA | | 14-0 | 52-35-11 | S10181 | | 1 | C | | | SP00184 | 9 | | 115-199 |
| 0231 | 22 | | GA | | 14-0 | 52-35-11 | S10181 | | 6 | C | | | SP00186 | 9 | | 115-199 |
| 0232 | 20 | | GA | | 105-0 | 28-25-11 | D41640P | | 23 | | | | D41855P | 18 | | 115-199 |
| 0233 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 25 | | | | D41640P | 24 | | 115-199 |
| 0234 | 22 | | GA | | 104-0 | 32-42-12 | D42184P | | 26 | | | | D41640P | 25 | | 115-199 |
| 0241 | 20 | | GA | | 103-0 | 21-51-22 | D42196P | | 48 | | | | D41640P | 26 | | 115-199 |
| 0242 | 24 | | GK | | 106-0 | SPARE | D41855P | | 55 | | | | D41640P | 27 | | 115-199 |
| 0243 | 24 | | GK | | 106-0 | SPARE | D41855P | | 54 | | | | D41640P | 28 | | 115-199 |
| 2000B | 24 | | GL | AD | 104-0 | SPARE | D41638P | | 37 | | | | D42190P | 37 | | 115-199 |
| 2000R | 24 | | GL | AD | 0-0 | SPARE | D41638P | | 38 | | | | D42190P | 38 | | 115-199 |
| 2001B | 24 | | GL | AA | 96-0 | 21-61-21 | D02566 | | 2 | | | | D42186P | 35 | | 115-199 |
| 2001R | 24 | | GL | AA | 0-0 | 21-61-21 | D02566 | | 1 | | | | D42186P | 34 | | 115-199 |
| 2004B | 24 | | GL | AE | 104-0 | SPARE | D41642P | | 39 | | | | D42190P | 39 | | 115-199 |
| 2004R | 24 | | GL | AE | 0-0 | SPARE | D41642P | | 40 | | | | D42190P | 40 | | 115-199 |
| 2011B | 24 | | GL | AL | 19-0 | 21-65-12 | D41642P | | 19 | | | | D04652 | A | | 115-199 |
| 2011R | 24 | | GL | AL | 0-0 | 21-65-12 | D41642P | | 20 | | | | SM00012 | | 9 | 115-199 |
| 2019B | 24 | | GL | AT | 18-0 | 21-65-12 | D41642P | | 21 | | | | D04650 | A | | 115-199 |
| 2019R | 24 | | GL | AT | 0-0 | 21-65-12 | D41642P | | 22 | | | | SM00011 | | 9 | 115-199 |
| 2020B | 24 | | GL | AU | 107-0 | 21-51-22 | D41855P | | 9 | | | | D41638P | 7 | | 115-199 |
| 2020R | 24 | | GL | AU | 0-0 | 21-51-22 | D41855P | | 10 | | | | D41638P | 8 | | 115-199 |
| 2021B | 24 | | GL | BF | 8-0 | 21-51-24 | D42186P | | 3 | | | | D41855P | 31 | | 115-199 |
| 2021R | 24 | | GL | BF | 0-0 | 21-51-24 | D42186P | | 2 | | | | D41855P | 30 | | 115-199 |
| 2022B | 24 | | GL | BG | 8-0 | 21-51-24 | D42196P | | 31 | | | | D41855P | 14 | | 115-199 |
| 2022R | 24 | | GL | BG | 0-0 | 21-51-24 | D42196P | | 32 | | | | D41855P | 15 | | 115-199 |
| 2023B | 24 | | GL | BH | 105-0 | 21-51-24 | D42186P | | 5 | | | | D41638P | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2710

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2716 | 286N2716 | | | RIGHT STA 820 TO E-6 RACK - AIR COND. SYSTEM. (continued) | | | | | | | | | | | |
| 2023R | 24 | GL | BH | | 0-0 | 21-51-24 | D42186P | | 4 | | D41638P | 10 | | | 115-199 |
| 2024B | 24 | GL | BI | | 105-0 | 21-51-24 | D42186P | | 7 | | D41638P | 11 | | | 115-199 |
| 2024R | 24 | GL | BI | | 0-0 | 21-51-24 | D42186P | | 6 | | D41638P | 12 | | | 115-199 |
| 2025B | 24 | GL | BJ | | 107-0 | 21-51-24 | D41855P | | 20 | | D41638P | 13 | | | 115-199 |
| 2025R | 24 | GL | BJ | | 0-0 | 21-51-24 | D41855P | | 19 | | D41638P | 14 | | | 115-199 |
| 2026B | 24 | GL | BK | | 105-0 | 21-51-25 | D42196P | | 41 | | D41638P | 15 | | | 115-199 |
| 2026R | 24 | GL | BK | | 0-0 | 21-51-25 | D42196P | | 42 | | D41638P | 16 | | | 115-199 |
| 2027B | 24 | GL | BL | | 104-0 | 21-61-11 | D42186P | | 22 | | D41640P | 29 | | | 115-199 |
| 2027R | 24 | GL | BL | | 0-0 | 21-61-11 | D42186P | | 21 | | D41640P | 30 | | | 115-199 |
| 2028B | 24 | GL | BM | | 104-0 | 21-61-11 | D42186P | | 20 | | D41640P | 31 | | | 115-199 |
| 2028R | 24 | GL | BM | | 0-0 | 21-61-11 | D42186P | | 19 | | D41640P | 32 | | | 115-199 |
| 2030B | 24 | GL | CA | | 103-0 | 21-51-22 | D42196P | | 43 | | D41640P | 33 | | | 115-199 |
| 2030R | 24 | GL | CA | | 0-0 | 21-51-22 | D42196P | | 44 | | D41640P | 34 | | | 115-199 |
| 2031B | 24 | GL | BS | | 103-0 | 21-51-12 | D41640P | | 35 | | D42196P | 54 | | | 115-199 |
| 2031R | 24 | GL | BS | | 0-0 | 21-51-12 | D41640P | | 36 | | D42196P | 53 | | | 115-199 |
| 2033B | 24 | GL | CH | | 94-0 | 21-61-31 | D02580 | | 2 | | D42186P | 51 | | | 115-199 |
| 2033R | 24 | GL | CH | | 0-0 | 21-61-31 | D02580 | | 1 | | D42186P | 50 | | | 115-199 |
| 2034B | 24 | GL | CJ | | 76-0 | 21-61-31 | D02582 | | 2 | | D42186P | 53 | | | 115-199 |
| 2034R | 24 | GL | CJ | | 0-0 | 21-61-31 | D02582 | | 1 | | D42186P | 52 | | | 115-199 |
| 2035B | 24 | GL | CK | | 8-0 | 21-51-22 | D42196P | | 11 | | D41855P | 12 | | | 115-199 |
| 2035R | 24 | GL | CK | | 0-0 | 21-51-22 | D42196P | | 12 | | D41855P | 11 | | | 115-199 |
| 2049B | 24 | GL | DA | | 103-0 | 21-51-22 | D42196P | | 29 | | D41640P | 37 | | | 115-199 |
| 2049R | 24 | GL | DA | | 0-0 | 21-51-22 | D42196P | | 30 | | D41640P | 38 | | | 115-199 |
| 2051B | 24 | GL | DB | | 105-0 | 21-51-22 | D42196P | | 33 | | D41638P | 17 | | | 115-199 |
| 2051R | 24 | GL | DB | | 0-0 | 21-51-22 | D42196P | | 34 | | D41638P | 18 | | | 115-199 |
| 2054B | 24 | GL | DC | | 104-0 | 21-51-22 | D42196P | | 10 | | D41642P | 23 | | | 115-199 |
| 2054R | 24 | GL | DC | | 0-0 | 21-51-22 | D42196P | | 9 | | D41642P | 24 | | | 115-199 |
| 2055B | 24 | GL | DE | | 104-0 | 21-61-11 | D41640P | | 39 | | D42186P | 37 | | | 115-199 |
| 2055R | 24 | GL | DE | | 0-0 | 21-61-11 | D41640P | | 40 | | D42186P | 36 | | | 115-199 |
| 3001B | 24 | GM | AV | | 105-0 | 21-51-22 | D42190P | | 14 | | D41638P | 19 | | | 115-199 |
| 3001R | 24 | GM | AV | | 0-0 | 21-51-22 | D42190P | | 13 | | D41638P | 20 | | | 115-199 |
| 3001Y | 24 | GM | AV | | 0-0 | 21-51-22 | D42190P | | 15 | | D41638P | 21 | | | 115-199 |
| 3002B | 24 | GM | AW | | 105-0 | 21-51-22 | D42190P | | 17 | | D41638P | 22 | | | 115-199 |
| 3002R | 24 | GM | AW | | 0-0 | 21-51-22 | D42190P | | 16 | | D41638P | 23 | | | 115-199 |
| 3002Y | 24 | GM | AW | | 0-0 | 21-51-22 | D42190P | | 18 | | D41638P | 24 | | | 115-199 |
| 3003B | 24 | GM | AX | | 105-0 | 21-51-22 | D42190P | | 19 | | D41638P | 25 | | | 115-199 |
| 3003R | 24 | GM | AX | | 0-0 | 21-51-22 | D42190P | | 20 | | D41638P | 26 | | | 115-199 |
| 3003Y | 24 | GM | AX | | 0-0 | 21-51-22 | D42190P | | 21 | | D41638P | 27 | | | 115-199 |
| 3004B | 24 | GM | AY | | 105-0 | 21-51-22 | D42190P | | 23 | | D41638P | 28 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2710

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2716 | 286N2716 | | | RIGHT STA 820 TO E-6 RACK - AIR COND. SYSTEM. (continued) | | | | | | | | | | | |
| 3004R | 24 | | GM | AY | 0-0 | 21-51-22 | D42190P | 22 | | | D41638P | 29 | | | 115-199 |
| 3004Y | 24 | | GM | AY | 0-0 | 21-51-22 | D42190P | 24 | | | D41638P | 30 | | | 115-199 |
| 3005B | 24 | | GM | BA | 105-0 | 21-51-22 | D42190P | 29 | | | D41638P | 31 | | | 115-199 |
| 3005R | 24 | | GM | BA | 0-0 | 21-51-22 | D42190P | 28 | | | D41638P | 32 | | | 115-199 |
| 3005Y | 24 | | GM | BA | 0-0 | 21-51-22 | D42190P | 30 | | | D41638P | 33 | | | 115-199 |
| 3006B | 24 | | GM | BB | 105-0 | 21-51-22 | D42190P | 26 | | | D41638P | 34 | | | 115-199 |
| 3006R | 24 | | GM | BB | 0-0 | 21-51-22 | D42190P | 25 | | | D41638P | 35 | | | 115-199 |
| 3006Y | 24 | | GM | BB | 0-0 | 21-51-22 | D42190P | 27 | | | D41638P | 36 | | | 115-199 |
| 3007B | 24 | | GM | BN | 104-0 | 21-61-11 | D42186P | 9 | | | D41640P | 41 | | | 115-199 |
| 3007R | 24 | | GM | BN | 0-0 | 21-61-11 | D42186P | 8 | | | D41640P | 42 | | | 115-199 |
| 3007Y | 24 | | GM | BN | 0-0 | 21-61-11 | D42186P | 10 | | | D41640P | 43 | | | 115-199 |
| 3008B | 24 | | GM | BO | 104-0 | 21-61-21 | D42186P | 24 | | | D41640P | 44 | | | 115-199 |
| 3008R | 24 | | GM | BO | 0-0 | 21-61-21 | D42186P | 23 | | | D41640P | 45 | | | 115-199 |
| 3008Y | 24 | | GM | BO | 0-0 | 21-61-21 | D42186P | 25 | | | D41640P | 46 | | | 115-199 |
| 3009B | 24 | | GM | BQ | 104-0 | 21-61-31 | D42186P | 48 | | | D41640P | 47 | | | 115-199 |
| 3009R | 24 | | GM | BQ | 0-0 | 21-61-31 | D42186P | 47 | | | D41640P | 48 | | | 115-199 |
| 3009Y | 24 | | GM | BQ | 0-0 | 21-61-31 | D42186P | 49 | | | D41640P | 49 | | | 115-199 |
| 3010B | 24 | | GM | BR | 104-0 | 21-61-21 | D42186P | 32 | | | D41642P | 25 | | | 115-199 |
| 3010R | 24 | | GM | BR | 0-0 | 21-61-21 | D42186P | 31 | | | D41642P | 26 | | | 115-199 |
| 3010Y | 24 | | GM | BR | 0-0 | 21-61-21 | D42186P | 33 | | | D41642P | 27 | | | 115-199 |
| 3011B | 24 | | GM | BT | 105-0 | 21-51-22 | D42196P | 46 | | | D41638P | 50 | | | 115-199 |
| 3011R | 24 | | GM | BT | 0-0 | 21-51-22 | D42196P | 45 | | | D41638P | 51 | | | 115-199 |
| 3011Y | 24 | | GM | BT | 0-0 | 21-51-22 | D42196P | 47 | | | D41638P | 52 | | | 115-199 |
| 3017B | 24 | | GM | CE | 104-0 | 21-61-31 | D41642P | 28 | | | D42186P | 40 | | | 115-199 |
| 3017R | 24 | | GM | CE | 0-0 | 21-61-31 | D41642P | 29 | | | D42186P | 41 | | | 115-199 |
| 3017Y | 24 | | GM | CE | 0-0 | 21-61-31 | D41642P | 30 | | | D42186P | 39 | | | 115-199 |
| 3018B | 24 | | GM | CF | 104-0 | 21-61-11 | D42186P | 17 | | | D41642P | 31 | | | 115-199 |
| 3018R | 24 | | GM | CF | 0-0 | 21-61-11 | D42186P | 16 | | | D41642P | 32 | | | 115-199 |
| 3018Y | 24 | | GM | CF | 0-0 | 21-61-11 | D42186P | 18 | | | D41642P | 33 | | | 115-199 |
| 5001B | 22 | | GU | DD | 104-0 | 32-42-11 | D42184P | 11 | | | D41640P | 50 | | | 115-199 |
| 5001R | 22 | | GU | DD | 0-0 | 32-42-11 | D42184P | 10 | | | D41640P | 51 | | | 115-199 |
| 5001Z | | | | DD | 0-0 | 32-42-11 | D42184P | 12 | | | D41640P | 52 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2710

Page 5 End

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W2720
Page 1
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|---------------------|------------------|------------------------------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip | Term Type Splice | Equip Term Type Splice Effectivity |
| W2727 | 286N2727 | LEFT ADF ANTENNA (continued) | | | |
| 8991ZC | | 1C | 0-0 34-57-11 D00267 | AB | D41999P 9 115-199 |
| FRAA | | | 0-0 34-57-11 D00267 | AA | GD00086 ST.. E 115-199 |
| W2728 | 286N2728 | RIGHT STA 820 TO FWD AND AFT TEMP SENSORS. | | | |
| 0037 | 24 GK | 35-11 21-61-31 | D02578 | 1 | D41640P 4 001-099 |
| 0038 | 20 GA | 2-0 21-61-31 | D02578 | 2 | GD01489 DC.. E 001-099 |
| 0039 | 24 GK | 35-1 21-61-21 | D02564 | 1 | D41640P 1 001-099 |
| 0040 | 20 GA | 3-6 21-61-21 | D02564 | 2 | GD01490 DC.. E 001-099 |
| 0119 | 24 GK | 3-3 21-65-12 | D04650 | B | SM00011 9 001-099 |
| 0120 | 24 GK | 4-10 21-65-12 | D04652 | B | SM00012 9 001-099 |
| 0133 | 20 GA | 3-11 21-65-12 | GD01490 | DC.. E | SM00011 9 001-099 |
| 0134 | 20 GA | 4-5 21-65-12 | GD01489 | DC.. E | SM00012 9 001-099 |
| 2001B | 24 GL AA | 35-3 21-61-21 | D02566 | 2 | D41640P 3 001-099 |
| 2001R | 24 GL AA | 0-0 21-61-21 | D02566 | 1 | D41640P 2 001-099 |
| 2011B | 24 GL AL | 35-9 21-65-12 | D41640P | 17 | D04652 A 001-099 |
| 2011R | 24 GL AL | 0-0 21-65-12 | D41640P | 19 | SM00012 9 001-099 |
| 2019B | 24 GL AT | 34-6 21-65-12 | D41640P | 13 | D04650 A 001-099 |
| 2019R | 24 GL AT | 0-0 21-65-12 | D41640P | 15 | SM00011 9 001-099 |
| 2033B | 24 GL CH | 35-9 21-61-31 | D02580 | 2 | D41640P 6 001-099 |
| 2033R | 24 GL CH | 0-0 21-61-31 | D02580 | 1 | D41640P 5 001-099 |
| 2034B | 24 GL CJ | 62-9 21-61-31 | D02582 | 2 | D41640P 7 001-099 |
| 2034R | 24 GL CJ | 0-0 21-61-31 | D02582 | 1 | D41640P 8 001-099 |
| W2729 | 286N2729 | RIGHT ADF ANTENNA (PROV) | | | |
| 0001 | 20 GA | 2-0 34-57-21 | D00445 | AB | GD00085 ST.. E 001-099 |
| 0001 | 20 GA | 1-6 34-57-21 | D00445 | AB | GD00085 ST.. E 115-199 |
| 0003 | 20 GA | 2-0 34-57-21 | D00445 | 14 | GD00085 ST.. E 001-099 |
| 0003 | 20 GA | 1-6 34-57-21 | D00445 | 14 | GD00085 ST.. E 115-199 |
| 8991B | 24 V2 1A | 0-0 34-57-21 | D00445 | 2 | D41993P 2 ALL |
| 8991G | 24 V2 1B | 0-0 34-57-21 | D00445 | 5 | D41993P 5 ALL |
| 8991K | 24 V2 1C | 0-0 34-57-21 | D00445 | 8 | D41993P 8 ALL |
| 8991N | 22 V2 1D | 0-0 34-57-21 | D00445 | 11 | D41993P 11 ALL |
| 8991O | 22 V2 1D | 0-0 34-57-21 | D00445 | 10 | D41993P 10 ALL |
| 8991R | 24 V2 1A | 0-0 34-57-21 | D00445 | 1 | D41993P 1 ALL |
| 8991V | 24 V2 1C | 0-0 34-57-21 | D00445 | 7 | D41993P 7 ALL |
| 8991W | 20 V2 1E | 50-0 34-57-21 | D00445 | 12 | D41993P 12 001-099 |
| 8991W | 20 V2 1E | 62-0 34-57-21 | D00445 | 12 | D41993P 12 115-199 |
| 8991Y | 24 V2 1B | 0-0 34-57-21 | D00445 | 4 | D41993P 4 ALL |
| 8991Z | | 0-0 34-57-21 | GD00085 | ST.. E | D41993P 21 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2720

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | | Effectivity |
|------------------------|-------------|----|----|--------------------------------------|---------|----------|--------|------|--------|-------|---------|------|--------|--|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2729 | 286N2729 | | | RIGHT ADF ANTENNA (PROV) (continued) | | | | | | | | | | | |
| 8991Z | | | | 1E | 0-0 | 34-57-21 | D00445 | | | AA | D41993P | 21 | 18 | | 115-199 |
| 8991ZA | | | | 1A | 0-0 | 34-57-21 | D00445 | | | AB | D41993P | 3 | | | ALL |
| 8991ZB | | | | 1B | 0-0 | 34-57-21 | D00445 | | | AB | D41993P | 6 | | | ALL |
| 8991ZC | | | | 1C | 0-0 | 34-57-21 | D00445 | | | AB | D41993P | 9 | | | ALL |
| FRAA | | | | | 0-0 | 34-57-21 | D00445 | | | AA | GD00085 | ST.. | E | | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W2720
Page 3 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2733 | 286N2733 | | | E3-3 SHELF TO LH. BRAKE PRESSURE XMTRS | | | | | | | | | | | |
| 0001 | 20 | | GA | | 66-0 | 31-31-52 | D41113P | | 1 | | D01505 | | 1 | | 001-099 |
| 0002 | 20 | | GA | | 72-0 | 31-31-52 | D41113P | | 2 | | D01501 | | 1 | | 001-099 |
| 2001B | 20 | | GB | AA | 66-0 | 31-31-52 | D41113P | | 4 | | D01505 | | 3 | | 001-099 |
| 2001R | 20 | | GB | AA | 0-0 | 31-31-52 | D41113P | | 3 | | D01505 | | 2 | | 001-099 |
| 2002B | 20 | | GB | AB | 72-0 | 31-31-52 | D41113P | | 6 | | D01501 | | 3 | | 001-099 |
| 2002R | 20 | | GB | AB | 0-0 | 31-31-52 | D41113P | | 5 | | D01501 | | 2 | | 001-099 |
| W2735 | 286N2735 | | | E3-3 SHELF TO RH. BRAKE PRESSURE XMTRS | | | | | | | | | | | |
| 0001 | 20 | | GA | | 69-0 | 31-31-52 | D41115P | | 1 | | D01507 | | 1 | | 001-099 |
| 0002 | 20 | | GA | | 80-0 | 31-31-52 | D41115P | | 2 | | D01503 | | 1 | | 001-099 |
| 2001B | 20 | | GB | AA | 69-0 | 31-31-52 | D41115P | | 4 | | D01507 | | 3 | | 001-099 |
| 2001R | 20 | | GB | AA | 0-0 | 31-31-52 | D41115P | | 3 | | D01507 | | 2 | | 001-099 |
| 2002B | 20 | | GB | AB | 80-0 | 31-31-52 | D41115P | | 6 | | D01503 | | 3 | | 001-099 |
| 2002R | 20 | | GB | AB | 0-0 | 31-31-52 | D41115P | | 5 | | D01503 | | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2730

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2800 | 286N2800 | | | APU F/W DISC TO P34 PANEL - APU GEN FEEDERS | | | | | | | | | | | |
| 0001 | *1 | | CQ | | 3-4 | 24-21-41 | SM00001 | | GX | | D40228J | A | | | ALL |
| 0002 | *1 | | CQ | | 3-3 | 24-21-41 | SM00002 | | GX | | D40228J | B | | | ALL |
| 0003 | *1 | | CQ | | 3-3 | 24-21-41 | SM00003 | | GX | | D40228J | C | | | ALL |
| 0004 | *2 | | 43 | | 141-0 | 24-21-41 | SM00001 | | GX | | SM00004 | | GX | | ALL |
| 0005 | *2 | | 43 | | 141-0 | 24-21-41 | SM00002 | | GX | | SM00005 | | GX | | ALL |
| 0006 | *2 | | 43 | | 141-0 | 24-21-41 | SM00003 | | GX | | SM00006 | | GX | | ALL |
| 0007 | 04 | | CQ | | 3-0 | 24-21-41 | D40228J | D | | | GD00202 | AC.. | H7 | | ALL |
| 0008 | *1 | | CQ | | 3-0 | 24-21-41 | SM00004 | | GX | | C00905 | L3 | R | | ALL |
| 0009 | *1 | | CQ | | 3-0 | 24-21-41 | SM00005 | | GX | | C00905 | L2 | R | | ALL |
| 0010 | *1 | | CQ | | 3-0 | 24-21-41 | SM00006 | | GX | | C00905 | L1 | R | | ALL |
| W2801 | 286N2801 | | | AFT BODY DISC TO LEFT ELEVATOR A/PILOT & ELEVATOR ASSYM LIMIT ACT CH L | | | | | | | | | | | |
| 0001 | 20 | | GA | | 22-0 | 22-11-12 | D40491J | 1 | | | D00029 | 2 | | | ALL |
| 0002 | 20 | | GA | | 22-0 | 22-11-12 | D40491J | 35 | | | D00029 | 18 | | | ALL |
| 0003 | 20 | | GA | | 3-0 | 22-11-12 | D00029 | 17 | | | GD00009 | DC.. | E | | ALL |
| 0004 | 20 | | GA | | 3-0 | 22-11-12 | D00029 | 1 | | | GD00009 | DC.. | E | | ALL |
| 0005 | 20 | | GA | | 3-0 | 22-11-12 | D00029 | 19 | | | GD00010 | ST.. | E | | ALL |
| 0006 | 20 | | GA | | 21-0 | 27-31-12 | D40491J | 13 | | | D00689 | 2 | | | ALL |
| 0007 | 20 | | GA | | 21-0 | 27-31-12 | D40491J | 14 | | | D00689 | 3 | | | ALL |
| 0008 | 20 | | GA | | 21-0 | 27-31-12 | D40491J | 15 | | | D00689 | 4 | | | ALL |
| 0009 | 20 | | GA | | 21-0 | 27-31-12 | D40491J | 16 | | | D00689 | 7 | | | ALL |
| 0010 | 20 | | GA | | 4-0 | 27-31-12 | D00689 | 1 | | | GD00513 | DC.. | E | | ALL |
| 0011 | 20 | | GA | | 4-0 | 27-31-12 | D00689 | 6 | | | GD00514 | ST.. | E | | ALL |
| 0019 | 18 | | GA | | 2-0 | 22-11-11 | GD01729 | ST.. | E | | D00913 | 6 | | | ALL |
| 0020 | 20 | | GA | | 4-0 | 27-31-12 | D00689 | 5 | | | GD00514 | ST.. | E | | ALL |
| 2003B | 20 | | GB | AH | 22-0 | 22-12-11 | D40491J | 12 | | | D00029 | 5 | | | ALL |
| 2003R | 20 | | GB | AH | 0-0 | 22-12-11 | D40491J | 11 | | | D00029 | 6 | | | ALL |
| 2004B | 20 | | GB | AB | 1-0 | 22-11-11 | SM00004 | | 9 | | D00029 | 12 | | | ALL |
| 2004R | 20 | | GB | AB | 0-0 | 22-11-11 | SM00003 | | 9 | | D00029 | 13 | | | ALL |
| 2005B | 20 | | GB | AC | 1-0 | 22-11-11 | SM00004 | | 9 | | D00029 | 7 | | | ALL |
| 2005R | 20 | | GB | AC | 0-0 | 22-11-11 | SM00003 | | 9 | | D00029 | 8 | | | ALL |
| 2006B | 20 | | GB | AA | 21-0 | 22-11-11 | D40491J | 3 | | | SM00004 | | 9 | | ALL |
| 2006R | 20 | | GB | AA | 0-0 | 22-11-11 | D40491J | 4 | | | SM00003 | | 9 | | ALL |
| 2013B | 20 | | GB | AW | 25-0 | 22-11-11 | D40491J | 2 | | | D00913 | 2 | | | ALL |
| 2013R | 20 | | GB | AW | 0-0 | 22-11-11 | D40491J | 34 | | | D00913 | 1 | | | ALL |
| 3001B | 20 | | GC | AD | 22-0 | 22-12-11 | D40491J | 6 | | | D00029 | 10 | | | ALL |
| 3001R | 20 | | GC | AD | 0-0 | 22-12-11 | D40491J | 5 | | | D00029 | 9 | | | ALL |
| 3001Y | 20 | | GC | AD | 0-0 | 22-12-11 | D40491J | 7 | | | D00029 | 11 | | | ALL |
| 3002B | 20 | | GC | AE | 22-0 | 22-12-11 | D40491J | 9 | | | D00029 | 15 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2800

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2801 | 286N2801 | | | AFT BODY DISC TO LEFT ELEVATOR A/PILOT & ELEVATOR ASSYM LIMIT ACT CH L (continued) | | | | | | | | | | | |
| 3002R | 20 | GC | AE | | 0-0 | 22-12-11 | D40491J | | 8 | | D00029 | 14 | | | ALL |
| 3002Y | 20 | GC | AE | | 0-0 | 22-12-11 | D40491J | | 10 | | D00029 | 16 | | | ALL |
| 3003B | 20 | GC | AJ | | 22-0 | 22-12-11 | D40491J | | 18 | | D00029 | CAP | Y | | ALL |
| 3003R | 20 | GC | AJ | | 0-0 | 22-12-11 | D40491J | | 17 | | D00029 | CAP | Y | | ALL |
| 3003Y | 20 | GC | AJ | | 0-0 | 22-12-11 | D40491J | | 19 | | D00029 | CAP | Y | | ALL |
| 3009B | 20 | GC | AV | | 25-0 | 22-12-11 | D40491J | | 37 | | D00913 | 3 | | | ALL |
| 3009R | 20 | GC | AV | | 0-0 | 22-12-11 | D40491J | | 36 | | D00913 | 5 | | | ALL |
| 3009Y | 20 | GC | AV | | 0-0 | 22-12-11 | D40491J | | 38 | | D00913 | 4 | | | ALL |
| W2802 | 286N2802 | | | APU FIREWALL DISC TO APU CRANK CONTACTOR (E6) | | | | | | | | | | | |
| 0001 | *1 | | CQ | | 4-6 | 49-41-11 | D40222J | | A | | SM00001 | | GX | | ALL |
| 0002 | *1 | | CQ | | 4-6 | 49-41-11 | D40222J | | B | | SM00002 | | GX | | ALL |
| 0003 | *3 | | 43 | | 39-0 | 49-41-11 | SM00001 | | | GX | TB5048 | 3 | H3 | | 001-099 |
| 0003 | *3 | | 43 | | 22-11 | 49-41-11 | SM00001 | | | GX | TB5048 | 3 | H3 | | 115-199 |
| 0004 | *3 | | 43 | | 39-0 | 49-41-11 | SM00002 | | | GX | TB5048 | 2 | H3 | | 001-099 |
| 0004 | *3 | | 43 | | 22-11 | 49-41-11 | SM00002 | | | GX | TB5048 | 2 | H3 | | 115-199 |
| 0005 | *1 | | CQ | | 2-11 | 49-41-11 | D40222J | | C | | GD00365 | DC.. | H8 | | ALL |
| 0006 | *1 | | CQ | | 2-11 | 49-41-11 | D40222J | | D | | GD00365 | DC.. | H8 | | ALL |
| W2803 | 286N2803 | | | AA1715 TO LEFT STAB TRIM CONTROL-CHANNEL LA | | | | | | | | | | | |
| 0001Y | 20 | | QB | | 6-0 | 27-41-11 | D01851 | | 1 | | GD01043 | DC.. | E | | ALL |
| 0002Y | 20 | | QB | | 14-0 | 27-41-11 | D01851 | | 3 | | D40697J | 1 | | | ALL |
| 0003Y | 20 | | QB | | 14-0 | 27-41-11 | D01851 | | 2 | | D40697J | 2 | | | ALL |
| 0004Y | 20 | | QB | | 28-0 | 27-41-11 | D01829 | | 2 | | D01837 | 21 | | | ALL |
| 0005Y | 20 | | QB | | 3-0 | 27-41-11 | D01829 | | 1 | | GD01043 | DC.. | E | *2 | ALL |
| 0006Y | 20 | | QB | | 3-0 | 27-41-11 | D01829 | | 5 | | GD01043 | DC.. | E | *2 | ALL |
| 0007Y | 20 | | QB | | 28-0 | 27-41-11 | D01829 | | 6 | | D01837 | 24 | | | ALL |
| 0008Y | 20 | | QB | | 19-0 | 27-41-11 | D40697J | | 3 | | D01837 | 18 | | | ALL |
| 0010Y | 20 | | QB | | 19-0 | 27-41-11 | D40697J | | 5 | | D01837 | 20 | | | ALL |
| 0011Y | 20 | | QB | | 19-0 | 27-41-11 | D40697J | | 4 | | D01837 | 19 | | | ALL |
| 0013 | 20 | | GA | | 2-0 | 27-48-21 | D01837 | | 31 | | GD01044 | ST.. | E | | ALL |
| 0014 | 20 | | GA | | 2-0 | 27-48-11 | D01837 | | 10 | | GD00879 | AC.. | E | | ALL |
| 0015 | 20 | | GA | | 2-0 | 27-48-11 | D01837 | | 5 | | GD00879 | AC.. | E | | ALL |
| 0016 | 20 | | GA | | 19-0 | 27-48-11 | D01837 | | 1 | | D40697J | 13 | | | ALL |
| 0017 | 20 | | GA | | 19-0 | 27-48-11 | D01837 | | 9 | | D40697J | 14 | | | ALL |
| 0018 | 20 | | GA | | 19-0 | 27-48-11 | D01837 | | 8 | | D40697J | 15 | | | ALL |
| 0022 | 20 | | GA | | 4-0 | 27-41-11 | D01851 | | 8 | | GD01085 | ST.. | E | | ALL |
| 0023 | 20 | | GA | | 3-0 | 27-41-11 | D01829 | | 10 | | GD01085 | ST.. | E | | ALL |
| 0024Y | 18 | | QB | | 3-0 | 27-41-31 | D01829 | | 3 | | GD01043 | DC.. | E | *1 | ALL |

WIRE LIST

D280N032

91-21-11

Section W2800

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|---|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2803 286N2803 AA1715 TO LEFT STAB TRIM CONTROL-CHANNEL LA (continued) | | | | | | | | | | | | | | | |
| 0025Y | 18 | | QB | | 3-0 | 27-41-31 | D01829 | | 7 | | GD01043 | DC.. | E | *1 | ALL |
| 0026Y | 20 | | QB | | 17-0 | 27-41-31 | D01829 | | 4 | | SP00391 | | 9 | | ALL |
| 0027Y | 20 | | QB | | 17-0 | 27-41-31 | D01829 | | 8 | | SP00389 | | 9 | | ALL |
| 2001B | 20 | | GB | AB | 19-0 | 27-48-21 | D40697J | | 12 | | D01837 | | 6 | | ALL |
| 2001R | 20 | | GB | AB | 0-0 | 27-48-21 | D40697J | | 11 | | D01837 | | 7 | | ALL |
| 3001B | 20 | | GC | AA | 19-0 | 27-48-21 | D40697J | | 9 | | D01837 | | 3 | | ALL |
| 3001R | 20 | | GC | AA | 0-0 | 27-48-21 | D40697J | | 8 | | D01837 | | 2 | | ALL |
| 3001Y | 20 | | GC | AA | 0-0 | 27-48-21 | D40697J | | 10 | | D01837 | | 4 | | ALL |
| W2805 286N2805 AA1715 TO LEFT STAB TRIM CONTROL-CHANNEL LB | | | | | | | | | | | | | | | |
| 0001Y | 20 | | QB | | 5-2 | 27-41-11 | D01831 | | 1 | | GD00015 | DC.. | E | *2 | ALL |
| 0002Y | 20 | | QB | | 5-2 | 27-41-11 | D01831 | | 5 | | GD00015 | DC.. | E | *2 | ALL |
| 0003Y | 20 | | QB | | 12-10 | 27-41-11 | D01831 | | 6 | | D40957J | | 1 | | ALL |
| 0004Y | 20 | | QB | | 12-10 | 27-41-11 | D01831 | | 2 | | D40957J | | 2 | | ALL |
| 0005 | 20 | | GA | | 15-1 | 27-41-11 | D01849 | | 1 | | D40957J | | 3 | | ALL |
| 0006 | 20 | | GA | | 2-5 | 27-41-11 | D01849 | | 2 | | GD00015 | DC.. | E | | ALL |
| 0007Y | 20 | | QB | | 12-10 | 27-41-11 | D40957J | | 4 | | D01831 | CAP | Y | | ALL |
| 0008 | 20 | | GA | | 12-10 | 27-41-11 | D40957J | | 6 | | D01831 | CAP | Y | | ALL |
| 0009 | 20 | | GA | | 4-9 | 27-41-11 | D01831 | | 10 | | GD01086 | ST.. | E | | ALL |
| 0010Y | 18 | | QB | | 5-2 | 27-41-31 | D01831 | | 3 | | GD00015 | DC.. | E | *1 | ALL |
| 0011Y | 18 | | QB | | 5-2 | 27-41-31 | D01831 | | 7 | | GD00015 | DC.. | E | *1 | ALL |
| 2501B | 20 | | H5 | AC | 19-2 | 27-41-31 | D01831 | | 4 | | D41337J | | 2 | | ALL |
| 2501R | 20 | | H5 | AC | 0-0 | 27-41-31 | D01831 | | 8 | | D41337J | | 1 | | ALL |
| 2501Z | | | | AC | 0-0 | 27-41-31 | D01831 | DED | | | D41337J | DED | | | ALL |
| W2806 286N2806 APU F/W DISC TO APU GEN - APU GEN FEEDERS | | | | | | | | | | | | | | | |
| 0001 | *1 | | CQ | | 1-11 | 24-21-41 | D40228P | | A | | M00281 | T1 | R | | ALL |
| 0002 | *1 | | CQ | | 1-11 | 24-21-41 | D40228P | | B | | M00281 | T2 | R | | ALL |
| 0003 | *1 | | CQ | | 1-11 | 24-21-41 | D40228P | | C | | M00281 | T3 | R | | ALL |
| 0004 | 04 | | CQ | | 1-11 | 24-21-41 | D40228P | | D | | M00281 | N | R | | ALL |
| W2807 286N2807 VIDEO COAX M10668 JUNCTION BOX TO M10685 AFT INTERFACE BOX STA-1330 | | | | | | | | | | | | | | | |
| 001CO | | | | AC | 0-0 | 23-32-01 | D01281 | =C1 | | | D01313 | =C1 | | | ALL |
| 001CX | | 59 | | AC | 35-0 | 23-32-01 | D01281 | =A1 | | | D01313 | =A1 | | | 001-099 |
| 001CX | | 59 | | AC | 28-7 | 23-32-01 | D01281 | =A1 | | | D01313 | =A1 | | | 115-199 |
| W2808 286N2808 APU F/W DISC TO APU GEN - APU GEN CONTROL | | | | | | | | | | | | | | | |
| 2501B | 18 | | HF | AC | 5-0 | 24-21-41 | D40230P | | 9 | | D02238 | | 10 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2800

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2808 | 286N2808 | | | APU F/W DISC TO APU GEN - APU GEN CONTROL (continued) | | | | | | | | | | | |
| 2501R | 18 | HF | AC | | 0-0 | 24-21-41 | D40230P | | 8 | | D02238 | | 9 | | ALL |
| 2501Z | | | AC | | 0-0 | 24-21-41 | D40230P | | 4 | | D02238 | DED | | | ALL |
| 3001B | 18 | HC | AA | | 5-0 | 24-21-41 | D40230P | | 6 | | D02238 | | 6 | | ALL |
| 3001R | 18 | HC | AA | | 0-0 | 24-21-41 | D40230P | | 5 | | D02238 | | 1 | | ALL |
| 3001Y | 18 | HC | AA | | 0-0 | 24-21-41 | D40230P | | 7 | | D02238 | | 7 | | ALL |
| 4001B | 20 | HD | AB | | 5-0 | 24-21-41 | D40230P | | 10 | | D02238 | | 13 | | ALL |
| 4001G | 20 | HD | AB | | 0-0 | 24-21-41 | D40230P | | 11 | | D02238 | | 3 | | ALL |
| 4001R | 20 | HD | AB | | 0-0 | 24-21-41 | D40230P | | 12 | | D02238 | | 12 | | ALL |
| 4001Y | 20 | HD | AB | | 0-0 | 24-21-41 | D40230P | | 13 | | D02238 | | 14 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2800

Page 4 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | |
|------------|-------------|-------|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2810 | 286N2810 | | | APU FIRE WALL DISC TO APU STARTER MOTOR | | | | | | | | | | |
| 0001 | *1 | CQ | | 5-10 | 49-41-11 | D40222P | | A | | M00893 | + | R | | 001-002, 115-199 |
| 0001 | *1 | CQ | | 5-10 | 49-41-11 | D40222P | | A | | M00893 | + | R | * | 003-099 |
| 0002 | *1 | CQ | | 5-10 | 49-41-11 | D40222P | | B | | M00893 | + | R | | 001-002, 115-199 |
| 0002 | *1 | CQ | | 5-10 | 49-41-11 | D40222P | | B | | M00893 | + | R | * | 003-099 |
| 0003 | *1 | CQ | | 5-10 | 49-41-11 | M00893 | | - | Q | D40222P | | C | | ALL |
| 0004 | *1 | CQ | | 5-10 | 49-41-11 | M00893 | | - | Q | D40222P | | D | | ALL |
| W2811 | 286N2811 | | | AFT BODY DISC. TO RIGHT ELEVATOR AUTOPILOT SERVO-CHANNEL R | | | | | | | | | | |
| 0001 | 20 | GA | | 29-0 | 22-11-22 | D40481J | | 1 | | D00069 | | 2 | | ALL |
| 0002 | 20 | GA | | 29-0 | 22-11-22 | D40481J | | 35 | | D00069 | | 18 | | ALL |
| 0003 | 20 | GA | | 3-0 | 22-11-22 | D00069 | | 17 | | GD00011 | DC.. | E | | ALL |
| 0004 | 20 | GA | | 3-0 | 22-11-22 | D00069 | | 1 | | GD00011 | DC.. | E | | ALL |
| 0005 | 20 | GA | | 3-0 | 22-11-22 | D00069 | | 19 | | GD00012 | ST.. | E | | ALL |
| 0019 | 18 | GA | | 2-0 | 22-11-21 | GD01730 | ST.. | E | | D00831 | | 6 | | ALL |
| 0029 | 20 | GA | | 3-0 | 27-31-11 | D00835 | | 1 | | GD01699 | DC.. | E | | ALL |
| 0030 | 20 | GA | | 16-0 | 27-31-11 | D00835 | | 2 | | SM00033 | | 9 | | ALL |
| 0031 | 20 | GA | | 3-0 | 27-31-11 | D00835 | | 3 | | GD01699 | DC.. | E | | ALL |
| 0032 | 20 | GA | | 16-0 | 27-31-11 | D00835 | | 4 | | SM00033 | | 9 | | ALL |
| 0033 | 20 | GA | | 2-0 | 27-31-11 | SM00033 | | 9 | | D40481J | | 33 | | ALL |
| 2003B | 20 | GB | AH | 29-0 | 22-12-21 | D40481J | | 12 | | D00069 | | 5 | | ALL |
| 2003R | 20 | GB | AH | 0-0 | 22-12-21 | D40481J | | 11 | | D00069 | | 6 | | ALL |
| 2004B | 20 | GB | AB | 29-0 | 22-11-21 | SM00004 | | 9 | | D00069 | | 12 | | ALL |
| 2004R | 20 | GB | AB | 0-0 | 22-11-21 | SM00003 | | 9 | | D00069 | | 13 | | ALL |
| 2005B | 20 | GB | AC | 29-0 | 22-11-21 | SM00004 | | 9 | | D00069 | | 7 | | ALL |
| 2005R | 20 | GB | AC | 0-0 | 22-11-21 | SM00003 | | 9 | | D00069 | | 8 | | ALL |
| 2006B | 20 | GB | AA | 2-0 | 22-11-21 | D40481J | | 3 | | SM00004 | | 9 | | ALL |
| 2006R | 20 | GB | AA | 0-0 | 22-11-21 | D40481J | | 4 | | SM00003 | | 9 | | ALL |
| 2013B | 20 | GB | AW | 29-0 | 22-11-21 | D40481J | | 2 | | D00831 | | 2 | | ALL |
| 2013R | 20 | GB | AW | 0-0 | 22-11-21 | D40481J | | 34 | | D00831 | | 1 | | ALL |
| 3001B | 20 | GC | AD | 29-0 | 22-12-21 | D40481J | | 6 | | D00069 | | 10 | | ALL |
| 3001R | 20 | GC | AD | 0-0 | 22-12-21 | D40481J | | 5 | | D00069 | | 9 | | ALL |
| 3001Y | 20 | GC | AD | 0-0 | 22-12-21 | D40481J | | 7 | | D00069 | | 11 | | ALL |
| 3002B | 20 | GC | AE | 29-0 | 22-12-21 | D40481J | | 9 | | D00069 | | 15 | | ALL |
| 3002R | 20 | GC | AE | 0-0 | 22-12-21 | D40481J | | 8 | | D00069 | | 14 | | ALL |
| 3002Y | 20 | GC | AE | 0-0 | 22-12-21 | D40481J | | 10 | | D00069 | | 16 | | ALL |
| 3005B | 20 | GC | AT | 29-0 | 22-12-21 | D40481J | | 30 | | D00069 | CAP | Y | | ALL |
| 3005R | 20 | GC | AT | 0-0 | 22-12-21 | D40481J | | 29 | | D00069 | CAP | Y | | ALL |
| 3005Y | 20 | GC | AT | 0-0 | 22-12-21 | D40481J | | 31 | | D00069 | CAP | Y | | ALL |
| 3009B | 20 | GC | AV | 29-0 | 22-12-21 | D40481J | | 37 | | D00831 | | 3 | | ALL |

WIRE LIST

D280N032

91-21-11
Section W2810
Page 1
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2811 | 286N2811 | | | AFT BODY DISC. TO RIGHT ELEVATOR AUTOPILOT SERVO-CHANNEL R (continued) | | | | | | | | | | | |
| 3009R | 20 | GC | AV | | 0-0 | 22-12-21 | D40481J | 36 | | | D00831 | 5 | | | ALL |
| 3009Y | 20 | GC | AV | | 0-0 | 22-12-21 | D40481J | 38 | | | D00831 | 4 | | | ALL |
| W2812 | 286N2812 | | | STA 1715 TO STA 1862 - LEFT STAB TRIM POS. XMTR | | | | | | | | | | | |
| 0001 | 20 | GA | | | 3-0 | 27-38-11 | D41112J | 1 | | | GD00881 | AC.. | E | | ALL |
| 0002 | 20 | GA | | | 22-0 | 27-38-11 | D41112J | 2 | | | D40120J | 1 | | | ALL |
| 0003 | 20 | GA | | | 19-0 | 27-23-11 | D04106 | 3 | | | D40120J | 4 | | | ALL |
| 0004 | 20 | GA | | | 2-0 | 27-23-11 | D04106 | 2 | | | GD02038 | DC.. | E | | ALL |
| 0005 | 20 | GA | | | 20-0 | 27-23-11 | D04104 | 1 | | | D40120J | 5 | | | ALL |
| 0006 | 20 | GA | | | 2-0 | 27-23-11 | D04104 | 2 | | | GD02038 | DC.. | E | | ALL |
| 0015 | 20 | GA | | | 22-0 | 33-45-11 | D40120J | 8 | | | D42044J | 1 | | | ALL |
| 0016 | 20 | GA | | | 22-0 | SPARE | D40120J | 9 | | | D42044J | 2 | | | ALL |
| 0017 | 20 | GA | | | 22-0 | 27-23-21 | D40120J | 6 | | | D41112J | 6 | | | ALL |
| 0018 | 20 | GA | | | 22-0 | 27-23-21 | D40120J | 7 | | | D41112J | 7 | | | ALL |
| 1001 | 20 | GE | AB | | 22-0 | 27-38-11 | D40120J | 12 | | | D41112J | 8 | | | ALL |
| 1001Z | | | AB | | 0-0 | 27-38-11 | D40120J | 13 | | | GD02619 | ST.. | E | | ALL |
| 2001B | 20 | GB | AA | | 22-0 | 27-38-11 | D41112J | 4 | | | D40120J | 3 | | | ALL |
| 2001R | 20 | GB | AA | | 0-0 | 27-38-11 | D41112J | 5 | | | D40120J | 2 | | | ALL |
| YAAA | | | | | 0-0 | 27-38-11 | GD02619 | ST.. | E | | GD02637 | ST.. | E | | ALL |
| W2813 | 286N2813 | | | AA1715 TO RIGHT STAB TRIM CONTROL-CHANNEL RB | | | | | | | | | | | |
| 0001Y | 20 | QB | | | 5-0 | 27-41-21 | D01847 | 1 | | | GD01045 | DC.. | E | | ALL |
| 0002Y | 20 | QB | | | 18-0 | 27-41-21 | D01847 | 3 | | | D40699J | 1 | | | ALL |
| 0003Y | 20 | QB | | | 18-0 | 27-41-21 | D01847 | 2 | | | D40699J | 2 | | | ALL |
| 0004Y | 20 | QB | | | 14-0 | 27-41-21 | D01833 | 2 | | | D01843 | 21 | | | ALL |
| 0005Y | 20 | QB | | | 5-0 | 27-41-21 | D01833 | 1 | | | GD01045 | DC.. | E | *1 | ALL |
| 0006Y | 20 | QB | | | 5-0 | 27-41-21 | D01833 | 5 | | | GD01045 | DC.. | E | *1 | ALL |
| 0007Y | 20 | QB | | | 14-0 | 27-41-21 | D01833 | 6 | | | D01843 | 24 | | | ALL |
| 0008Y | 20 | QB | | | 22-0 | 27-41-21 | D40699J | 5 | | | D01843 | 20 | | | ALL |
| 0010Y | 20 | QB | | | 22-0 | 27-41-21 | D40699J | 3 | | | D01843 | 18 | | | ALL |
| 0011Y | 20 | QB | | | 22-0 | 27-41-21 | D40699J | 4 | | | D01843 | 19 | | | ALL |
| 0013 | 20 | GA | | | 4-0 | 27-48-21 | D01843 | 31 | | | GD01046 | ST.. | E | | ALL |
| 0014 | 20 | GA | | | 3-0 | 27-48-11 | D01843 | 10 | | | GD02356 | AC.. | E | | ALL |
| 0015 | 20 | GA | | | 3-0 | 27-48-11 | D01843 | 5 | | | GD02356 | AC.. | E | | ALL |
| 0016 | 20 | GA | | | 22-0 | 27-48-11 | D01843 | 1 | | | D40699J | 13 | | | ALL |
| 0017 | 20 | GA | | | 22-0 | 27-48-11 | D01843 | 9 | | | D40699J | 14 | | | ALL |
| 0018 | 20 | GA | | | 22-0 | 27-48-11 | D01843 | 8 | | | D40699J | 15 | | | ALL |
| 0022 | 20 | GA | | | 4-0 | 27-41-21 | D01847 | 8 | | | GD01088 | ST.. | E | | ALL |
| 0023 | 20 | GA | | | 4-0 | 27-41-21 | D01833 | 10 | | | GD01088 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2810

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|-------------|--------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W2813 | 286N2813 | | | | AA1715 TO RIGHT STAB TRIM CONTROL-CHANNEL RB (continued) | | | | | | | | | | | |
| 0024Y | 18 | | QB | | 5-0 | 27-41-31 | D01833 | | 3 | | GD01045 | DC.. | E | *2 | ALL | |
| 0025Y | 18 | | QB | | 5-0 | 27-41-31 | D01833 | | 7 | | GD01045 | DC.. | E | *2 | ALL | |
| 0026Y | 20 | | QB | | 14-0 | 27-41-31 | D01843 | | 25 | | D01833 | | 8 | | ALL | |
| 0027Y | 20 | | QB | | 14-0 | 27-41-31 | D01843 | | 27 | | D01833 | | 4 | | ALL | |
| 2001B | 20 | | GB | AB | 22-0 | 27-48-21 | D40699J | | 12 | | D01843 | | 6 | | ALL | |
| 2001R | 20 | | GB | AB | 0-0 | 27-48-21 | D40699J | | 11 | | D01843 | | 7 | | ALL | |
| 2501B | 20 | | H5 | AC | 18-1 | 27-41-31 | D01843 | | 28 | | D41227J | | 2 | | ALL | |
| 2501R | 20 | | H5 | AC | 0-0 | 27-41-31 | D01843 | | 26 | | D41227J | | 1 | | ALL | |
| 2501Z | | | | AC | 0-0 | 27-41-31 | D01843 | DED | | | D41227J | DED | | | ALL | |
| 3001B | 20 | | GC | AA | 22-0 | 27-48-21 | D40699J | | 9 | | D01843 | | 3 | | ALL | |
| 3001R | 20 | | GC | AA | 0-0 | 27-48-21 | D40699J | | 8 | | D01843 | | 2 | | ALL | |
| 3001Y | 20 | | GC | AA | 0-0 | 27-48-21 | D40699J | | 10 | | D01843 | | 4 | | ALL | |
| W2814 | 286N2814 | | | | STA 1715 TO STA 1862 - RIGHT STAB TRIM POS. XMTR | | | | | | | | | | | |
| 0001 | 20 | | GA | | 2-8 | 27-38-11 | D41114J | | 1 | | GD00882 | AC.. | E | | ALL | |
| 0002 | 20 | | GA | | 27-1 | 27-38-11 | D41114J | | 2 | | D40164J | | 1 | | ALL | |
| 0003 | 20 | | GA | | 26-11 | 27-23-11 | D03434 | | 3 | | D40164J | | 4 | | ALL | |
| 0004 | 20 | | GA | | 2-9 | 27-23-11 | D03434 | | 2 | | GD02039 | DC.. | E | | ALL | |
| 0005 | 20 | | GA | | 27-0 | 27-23-11 | D03430 | | 1 | | D40164J | | 5 | | ALL | |
| 0006 | 20 | | GA | | 2-10 | 27-23-11 | D03430 | | 2 | | GD02039 | DC.. | E | | ALL | |
| 0015 | 20 | | HL | | 27-1 | 33-45-11 | D40164J | | 8 | | D42098J | | 1 | | ALL | |
| 0016 | 20 | | HL | | 27-1 | SPARE | D40164J | | 9 | | D42098J | | 2 | | ALL | |
| 0017 | 20 | | HL | | 27-1 | 27-23-21 | D40164J | | 6 | | D41114J | | 6 | | ALL | |
| 0018 | 20 | | HL | | 27-1 | 27-23-21 | D40164J | | 7 | | D41114J | | 7 | | ALL | |
| 1001 | 20 | | GE | AB | 27-1 | 27-38-11 | D40164J | | 10 | | D41114J | | 8 | | ALL | |
| 1001Z | | | | AB | 0-0 | 27-38-11 | D40164J | | 11 | | GD02613 | ST.. | E | | ALL | |
| 2001B | 20 | | GB | AA | 27-1 | 27-38-11 | D41114J | | 4 | | D40164J | | 3 | | ALL | |
| 2001R | 20 | | GB | AA | 0-0 | 27-38-11 | D41114J | | 5 | | D40164J | | 2 | | ALL | |
| YAAA | | | | | 0-0 | 27-38-11 | GD02613 | ST.. | E | | GD02615 | ST.. | E | | ALL | |
| W2815 | 286N2815 | | | | AA1715 TO RIGHT STAB TRIM CONTROL-CHANNEL RA | | | | | | | | | | | |
| 0001Y | 20 | | QB | | 5-0 | 27-41-21 | D01835 | | 1 | | GD00016 | DC.. | E | *2 | ALL | |
| 0002Y | 20 | | QB | | 5-0 | 27-41-21 | D01835 | | 5 | | GD00016 | DC.. | E | *2 | ALL | |
| 0003Y | 20 | | QB | | 19-0 | 27-41-21 | D01835 | | 6 | | D40959J | | 1 | | ALL | |
| 0004Y | 20 | | QB | | 19-0 | 27-41-21 | D01835 | | 2 | | D40959J | | 2 | | ALL | |
| 0005 | 20 | | GA | | 18-0 | 27-41-21 | D01845 | | 1 | | D40959J | | 3 | | ALL | |
| 0006 | 20 | | GA | | 4-0 | 27-41-21 | D01845 | | 2 | | GD00016 | DC.. | E | | ALL | |
| 0007Y | 20 | | QB | | 19-0 | 27-41-21 | D40959J | | 4 | | D01835 | CAP | Y | | ALL | |
| 0008 | 20 | | GA | | 19-0 | 27-41-21 | D40959J | | 6 | | D01835 | CAP | Y | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W2810

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|-----------------|------------------------|------------------------|
| Wire No. | GA CO TY | Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice |
| W2815 | 286N2815 | AA1715 TO RIGHT STAB TRIM CONTROL-CHANNEL RA (continued) | | | |
| 0009 | 20 | GA | 4-0 27-41-21 | D01835 10 | GD01087 ST.. E ALL |
| 0010Y | 18 | QB | 5-0 27-41-31 | D01835 3 | GD00016 DC.. E *1 ALL |
| 0011Y | 18 | QB | 5-0 27-41-31 | D01835 7 | GD00016 DC.. E *1 ALL |
| 2501B | 20 | H5 AC | 16-0 27-41-31 | D01835 4 | D41225J 2 ALL |
| 2501R | 20 | H5 AC | 0-0 27-41-31 | D01835 8 | D41225J 1 ALL |
| 2501Z | | AC | 0-0 27-41-31 | D01835 DED | D41225J DED ALL |
| W2817 | 286N2817 | VIDEO COAX M10668 JUNCTION BOX TO VIDEO MONITOR | | | |
| 001CO | | AA | 0-0 23-32-01 | D01277 =C1 | D01305 =C1 ALL |
| 001CX | 59 | AA | 109-2 23-32-01 | D01277 =A1 | D01305 =A1 001-099 |
| 001CX | 66 | AA | 104-11 23-32-01 | D01277 =A1 | D01305 =A1 115-199 |
| W2818 | 286N2818 | APU TAIL CONE COMPARTMENT LIGHTS | | | |
| 0003 | 22 | GA | 17-3 33-31-31 | D40258J 3 | D02258 4 001-099 |
| 0003 | 22 | GA | 17-3 33-31-31 | D40258P 3 | D02258 3 115-199 |
| 0007 | 20 | GA | 44-2 33-31-31 | S00427 1 C | S00443 1 C ALL |
| 0008 | 20 | GA | 52-8 33-31-31 | S00427 2 C | SP00204 9 ALL |
| 0009 | 20 | GA | 35-10 33-31-31 | S00443 2 C * | SP00308 9 ALL |
| 0010 | 20 | GA | 16-11 33-31-31 | S00443 2 C * | SP00310 9 ALL |
| 0011 | 20 | GA | 44-2 33-31-31 | S00427 3 C | S00443 3 C ALL |
| 0013 | 20 | GA | 29-6 SPARE | D40258J 2 | D40230J 2 001-099 |
| 0013 | 20 | GA | 29-6 SPARE | D40258P 2 | D40230J 2 115-199 |
| 0014 | 20 | GA | 29-6 SPARE | D40258J 14 | D40230J 14 001-099 |
| 0014 | 20 | GA | 29-6 SPARE | D40258P 14 | D40230J 14 115-199 |
| 0015 | 20 | GA | 23-2 33-31-31 | SP00310 9 | SP00564 9 ALL |
| 0016 | 20 | GA | 28-7 33-31-31 | D02258 5 | S00427 2 C ALL |
| 0017 | 20 | GA | 2-3 33-31-31 | D02258 1 | GD00586 AC.. E ALL |
| 0018 | 20 | GA | 2-3 33-31-31 | D02258 6 | GD00585 ST.. E ALL |
| 0019 | 20 | GA | 13-0 33-31-31 | SP00310 9 | SP00334 9 ALL |
| 2501B | 20 | GF AB | 29-6 24-21-41 | D40258J 9 | D40230J 9 001-099 |
| 2501B | 20 | GF AB | 29-6 24-21-41 | D40258P 9 | D40230J 9 115-199 |
| 2501R | 20 | GF AB | 0-0 24-21-41 | D40258J 8 | D40230J 8 001-099 |
| 2501R | 20 | GF AB | 0-0 24-21-41 | D40258P 8 | D40230J 8 115-199 |
| 2501Z | | AB | 0-0 24-21-41 | D40258J 4 | D40230J 4 001-099 |
| 2501Z | | AB | 0-0 24-21-41 | D40258P 4 | D40230J 4 115-199 |
| 3001B | 18 | GC AA | 29-6 24-21-41 | D40258J 6 | D40230J 6 001-099 |
| 3001B | 18 | GC AA | 29-6 24-21-41 | D40258P 6 | D40230J 6 115-199 |
| 3001R | 18 | GC AA | 0-0 24-21-41 | D40258J 5 | D40230J 5 001-099 |
| 3001R | 18 | GC AA | 0-0 24-21-41 | D40258P 5 | D40230J 5 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2810

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|---|-------------|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2818 | 286N2818 | | | APU TAIL CONE COMPARTMENT LIGHTS (continued) | | | | | | | | | | | | |
| 3001Y | 18 | GC | AA | | 0-0 | 24-21-41 | | D40258J | | 7 | | D40230J | | 7 | | 001-099 |
| 3001Y | 18 | GC | AA | | 0-0 | 24-21-41 | | D40258P | | 7 | | D40230J | | 7 | | 115-199 |
| 4001B | 20 | GD | AC | | 29-6 | 24-21-41 | | D40258J | | 10 | | D40230J | | 10 | | 001-099 |
| 4001B | 20 | GD | AC | | 29-6 | 24-21-41 | | D40258P | | 10 | | D40230J | | 10 | | 115-199 |
| 4001G | 20 | GD | AC | | 0-0 | 24-21-41 | | D40258J | | 11 | | D40230J | | 11 | | 001-099 |
| 4001G | 20 | GD | AC | | 0-0 | 24-21-41 | | D40258P | | 11 | | D40230J | | 11 | | 115-199 |
| 4001R | 20 | GD | AC | | 0-0 | 24-21-41 | | D40258J | | 12 | | D40230J | | 12 | | 001-099 |
| 4001R | 20 | GD | AC | | 0-0 | 24-21-41 | | D40258P | | 12 | | D40230J | | 12 | | 115-199 |
| 4001Y | 20 | GD | AC | | 0-0 | 24-21-41 | | D40258J | | 13 | | D40230J | | 13 | | 001-099 |
| 4001Y | 20 | GD | AC | | 0-0 | 24-21-41 | | D40258P | | 13 | | D40230J | | 13 | | 115-199 |
| A-AG | | | | | 0-0 | 33-31-31 | | L00348 | | WHT | | GD00587 | | AC.. | E | ALL |
| A-AP | | | | | 0-0 | 33-31-31 | | SP00308 | | | 9 | L00348 | | BLK | | ALL |
| B-AG | | | | | 0-0 | 33-31-31 | | L00349 | | WHT | | GD00588 | | AC.. | E | ALL |
| B-AP | | | | | 0-0 | 33-31-31 | | SP00564 | | | 9 | L00349 | | BLK | | ALL |
| B-BG | | | | | 0-0 | 33-31-31 | | L00380 | | WHT | | GD00589 | | AC.. | E | ALL |
| B-BP | | | | | 0-0 | 33-31-31 | | SP00310 | | | 9 | L00380 | | BLK | | ALL |
| B-CG | | | | | 0-0 | 33-31-31 | | L00350 | | WHT | | GD00590 | | AC.. | E | ALL |
| B-CP | | | | | 0-0 | 33-31-31 | | L00350 | | BLK | | SP00334 | | | 9 | ALL |
| W2819 | 286N2819 | | | VIDEO COAX M10688 JUNCTION BOX TO VIDEO MOMITOR | | | | | | | | | | | | |
| 001CO | | | AB | | 0-0 | 23-32-01 | | D01279 | | = C1 | | D01309 | | = C1 | | ALL |
| 001CX | | 59 | AB | | 99-8 | 23-32-01 | | D01279 | | = A1 | | D01309 | | = A1 | | 001-099 |
| 001CX | | 66 | AB | | 92-0 | 23-32-01 | | D01279 | | = A1 | | D01309 | | = A1 | | 115-199 |

WIRE LIST

D280N032

91-21-11
Section W2810
Page 5 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2821 | | 286N2821 | | | | AFT BODY DISC.TO CENTER ELEVATOR AUTOPILOT SERVO CHANNEL C | | | | | | | | | |
| 0001 | 20 | GA | | | 24-6 | 22-11-32 | D40497J | 1 | | | D00049 | 2 | | | ALL |
| 0002 | 20 | GA | | | 24-6 | 22-11-32 | D40497J | 14 | | | D00049 | 18 | | | ALL |
| 0003 | 20 | GA | | | 2-6 | 22-11-32 | D00049 | 17 | | | GD00013 | DC.. | E | | ALL |
| 0004 | 20 | GA | | | 2-6 | 22-11-32 | D00049 | 1 | | | GD00013 | DC.. | E | | ALL |
| 0005 | 20 | GA | | | 2-6 | 22-11-32 | D00049 | 19 | | | GD00014 | ST.. | E | | ALL |
| 0006 | 20 | GA | | | 2-7 | 27-48-21 | D01841 | 31 | | | GD00418 | ST.. | E | | ALL |
| 0007Y | 20 | QB | | | 20-9 | 27-41-31 | D01841 | 25 | | | SP00389 | | 9 | | ALL |
| 0008Y | 20 | QB | | | 20-9 | 27-41-31 | D01841 | 27 | | | SP00391 | | 9 | | ALL |
| 0019 | 18 | GA | | | 2-6 | 22-11-31 | GD01731 | ST.. | E | | D00833 | 6 | | | ALL |
| 0025 | 18 | GA | | | 3-5 | 27-23-11 | D03432 | 2 | | | GD01973 | DC.. | E | | ALL |
| 0026 | 20 | GA | | | 22-0 | 27-23-11 | D03432 | 1 | | | D40497J | 26 | | | ALL |
| 0027 | 20 | GA | | | 22-0 | 27-23-11 | D03436 | 3 | | | D40497J | 27 | | | ALL |
| 0028 | 18 | GA | | | 3-5 | 27-23-11 | D03436 | 2 | | | GD01974 | DC.. | E | | ALL |
| 0029 | 20 | GA | | | 21-10 | 31-51-41 | D01841 | 22 | | | D40497J | 25 | | | ALL |
| 0030 | 20 | GA | | | 2-11 | 31-51-41 | D01841 | 23 | | | GD02257 | DC.. | E | | ALL |
| 2003B | 20 | GB | AH | | 24-6 | 22-12-31 | D40497J | 12 | | | D00049 | 5 | | | ALL |
| 2003R | 20 | GB | AH | | 0-0 | 22-12-31 | D40497J | 11 | | | D00049 | 6 | | | ALL |
| 2004B | 20 | GB | AB | | 2-3 | 22-11-31 | SM00004 | | 9 | | D00049 | 12 | | | ALL |
| 2004R | 20 | GB | AB | | 0-0 | 22-11-31 | SM00003 | | 9 | | D00049 | 13 | | | ALL |
| 2005B | 20 | GB | AC | | 2-3 | 22-11-31 | SM00004 | | 9 | | D00049 | 7 | | | ALL |
| 2005R | 20 | GB | AC | | 0-0 | 22-11-31 | SM00003 | | 9 | | D00049 | 8 | | | ALL |
| 2006B | 20 | GB | AA | | 22-9 | 22-11-31 | D40497J | 3 | | | SM00004 | | 9 | | ALL |
| 2006R | 20 | GB | AA | | 0-0 | 22-11-31 | D40497J | 4 | | | SM00003 | | 9 | | ALL |
| 2007B | 20 | GB | AK | | 21-10 | 27-48-21 | D01841 | 6 | | | D40497J | 17 | | | ALL |
| 2007R | 20 | GB | AK | | 0-0 | 27-48-21 | D01841 | 7 | | | D40497J | 16 | | | ALL |
| 2013B | 20 | GB | AW | | 27-10 | 22-11-31 | D40497J | 35 | | | D00833 | 2 | | | ALL |
| 2013R | 20 | GB | AW | | 0-0 | 22-11-31 | D40497J | 34 | | | D00833 | 1 | | | ALL |
| 2501B | 20 | H5 | AF | | 18-2 | 27-41-31 | D01841 | 28 | | | D41335J | 2 | | | ALL |
| 2501R | 20 | H5 | AF | | 0-0 | 27-41-31 | D01841 | 26 | | | D41335J | 1 | | | ALL |
| 2501Z | | | AF | | 0-0 | 27-41-31 | D01841 | DED | | | D41335J | DED | | | ALL |
| 3001B | 20 | GC | AD | | 24-6 | 22-12-31 | D40497J | 6 | | | D00049 | 10 | | | ALL |
| 3001R | 20 | GC | AD | | 0-0 | 22-12-31 | D40497J | 5 | | | D00049 | 9 | | | ALL |
| 3001Y | 20 | GC | AD | | 0-0 | 22-12-31 | D40497J | 7 | | | D00049 | 11 | | | ALL |
| 3002B | 20 | GC | AE | | 24-6 | 22-12-31 | D40497J | 9 | | | D00049 | 15 | | | ALL |
| 3002R | 20 | GC | AE | | 0-0 | 22-12-31 | D40497J | 8 | | | D00049 | 14 | | | ALL |
| 3002Y | 20 | GC | AE | | 0-0 | 22-12-31 | D40497J | 10 | | | D00049 | 16 | | | ALL |
| 3004B | 20 | GC | AJ | | 21-10 | 27-48-21 | D01841 | 3 | | | D40497J | 2 | | | ALL |
| 3004R | 20 | GC | AJ | | 0-0 | 27-48-21 | D01841 | 2 | | | D40497J | 13 | | | ALL |
| 3004Y | 20 | GC | AJ | | 0-0 | 27-48-21 | D01841 | 4 | | | D40497J | 15 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W2820

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2821 | 286N2821 | | | AFT BODY DISC.TO CENTER ELEVATOR AUTOPILOT SERVO CHANNEL C (continued) | | | | | | | | | | | |
| 3005B | 20 | GC | AL | | 24-6 | 22-12-31 | D40497J | 18 | | | D00049 | CAP | Y | | ALL |
| 3005R | 20 | GC | AL | | 0-0 | 22-12-31 | D40497J | 19 | | | D00049 | CAP | Y | | ALL |
| 3005Y | 20 | GC | AL | | 0-0 | 22-12-31 | D40497J | 20 | | | D00049 | CAP | Y | | ALL |
| 3009B | 20 | GC | AV | | 27-10 | 22-12-31 | D40497J | 37 | | | D00833 | 3 | | | ALL |
| 3009R | 20 | GC | AV | | 0-0 | 22-12-31 | D40497J | 36 | | | D00833 | 5 | | | ALL |
| 3009Y | 20 | GC | AV | | 0-0 | 22-12-31 | D40497J | 38 | | | D00833 | 4 | | | ALL |
| W2822 | 286N2822 | | | APU COMPARTMENT LIGHTING AND SERVICE INTERPHONE | | | | | | | | | | | |
| 0001 | 20 | HA | | | 6-0 | 33-31-31 | D40104P | 2 | | | S00428 | 2 | C | | ALL |
| 0002 | 20 | HA | | | 6-0 | SPARE | S00428 | 3 | C | * | D40104P | 6 | | | 115-199 |
| 0003 | 20 | HA | | | 5-2 | 33-31-31 | S00428 | 3 | C | | SP00336 | 9 | | | 001-099 |
| 0003 | 20 | HA | | | 5-2 | 33-31-31 | S00428 | 3 | C | * | SP00336 | 9 | | | 115-199 |
| 0004 | 20 | HA | | | 3-0 | 33-31-31 | SP00600 | 9 | | | D40104P | 7 | | | ALL |
| 0005 | 20 | HA | | | 9-3 | 33-31-31 | SP00336 | 9 | | | SP00064 | 9 | | | ALL |
| 0006 | 20 | HA | | | 9-3 | 33-31-31 | SP00600 | 9 | | | SP00108 | 9 | | | ALL |
| 0007 | 20 | HA | | | 6-3 | 33-31-31 | SP00336 | 9 | | | SP00480 | 9 | | | ALL |
| 0008 | 20 | HA | | | 6-3 | 33-31-31 | SP00600 | 9 | | | SP00482 | 9 | | | ALL |
| 2501B | 20 | HF | AB | | 4-7 | 23-41-12 | D40104P | 3 | | | SM00001 | 9 | | | 001-099 |
| 2501R | 20 | HF | AB | | 0-0 | 23-41-12 | D40104P | 4 | | | SM00002 | 9 | | | 001-099 |
| 2501Z | | | AB | | 0-0 | 23-41-12 | D40104P | 1 | | | SM00003 | 9 | | | 001-099 |
| 3501B | 20 | HG | AA | | 4-7 | 23-41-12 | D40104P | 3 | | | SM00001 | 9 | | | 115-199 |
| 3501R | 20 | HG | AA | | 0-0 | 23-41-12 | D40104P | 4 | | | SM00002 | 9 | | | 115-199 |
| 3501Y | 20 | HG | AA | | 0-0 | 23-41-12 | D40104P | 5 | | | SM00003 | 9 | | | 115-199 |
| 3501Z | | | AA | | 0-0 | 23-41-12 | D40104P | 1 | | | SM00003 | DED | | | 115-199 |
| A-B | | | | | 0-0 | 33-31-31 | L00351 | BLK | | | SP00336 | 9 | | | ALL |
| A-C | | | | | 0-0 | 23-41-12 | D00413 | BLU | | | SM00001 | 9 | | | ALL |
| A-D | | | | | 0-0 | 23-41-12 | D00413 | RED | | | SM00002 | 9 | | | ALL |
| A-E | | | | | 0-0 | 23-41-12 | D00413 | BLK | | | SM00003 | 9 | | | ALL |
| A-F | | | | | 0-0 | 33-31-31 | L00540 | BLK | | | SP00480 | 9 | | | ALL |
| A-G | | | | | 0-0 | 33-31-31 | L00540 | WHT | | | SP00482 | 9 | | | ALL |
| A-H | | | | | 0-0 | 33-31-31 | L00541 | BLK | | | SP00064 | 9 | | | ALL |
| A-J | | | | | 0-0 | 33-31-31 | L00541 | WHT | | | SP00108 | 9 | | | ALL |
| B-B | | | | | 0-0 | 33-31-31 | L00351 | WHT | | | SP00600 | 9 | | | ALL |
| W2823 | 286N2823 | | | VIDEO COAX M10668 JUNCTION BOX TO M10684 INTERFACE BOX STA-770 | | | | | | | | | | | |
| 001CO | | | AA | | 0-0 | 23-32-01 | D01275 | = C1 | | | D01293 | = C1 | | | ALL |
| 001CX | | 59 | AA | | 106-3 | 23-32-01 | D01275 | = A1 | | | D01293 | = A1 | | | 001-099 |
| 001CX | | 59 | AA | | 74-9 | 23-32-01 | D01275 | = A1 | | | D01293 | = A1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2820

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W2825 | 286N2825 | VOR LEFT ANTENNA | | | | | | | | | | | | | |
| 001CO | | AA | 0-0 | 34-51-11 | D00597 | = C1 | | | D40661P | = C1 | | | ALL | | |
| 001CX | 65 | AA | 44-11 | 34-51-11 | D00597 | = A1 | | | D40661P | = A1 | | | 001-099 | | |
| 001CX | BS | AA | 44-1 | 34-51-11 | D00597 | = A1 | | | D40661P | = A1 | | | 115-199 | | |
| W2826 | 286N2826 | APU F/W TO APU FIRE DET. ELEMENT (LOOP A) | | | | | | | | | | | | | |
| 0001 | 16 | VD | 6-0 | 26-15-11 | D40316P | 4 | | | D01900 | = 1 | | | 001-009 | | |
| 0001 | 16 | VD | 6-0 | 26-15-11 | D40316P | 4 | | | D01900 | = 1 | 16 | | 115-199 | | |
| 0001R | 16 | TJ | 6-0 | 26-15-11 | D40316P | 4 | | | D01900 | = 1 | | | 010-099 | | |
| 0002 | 16 | VD | 14-0 | 26-15-11 | D40316P | 6 | | | D01910 | = 1 | | | 001-009 | | |
| 0002 | 16 | VD | 13-0 | 26-15-11 | D40316P | 6 | | | D01910 | = 1 | | | 115-199 | | |
| 0002R | 16 | TJ | 14-0 | 26-15-11 | D40316P | 6 | | | D01910 | = 1 | | | 010-099 | | |
| 0003 | 16 | VD | 14-0 | 26-15-11 | D40316P | 2 | | | GD02634 | ST.. | E | | 001-009 | | |
| 0003 | 16 | VD | 6-0 | 26-15-11 | D40316P | 2 | | | GD02634 | ST.. | E | | 115-199 | | |
| 0003R | 16 | TJ | 14-0 | 26-15-11 | D40316P | 2 | | | GD02634 | ST.. | E | | 010-099 | | |
| 0004 | 16 | VD | 23-0 | 26-15-11 | D01902 | = 1 | | | D01908 | = 1 | | | 001-009 | | |
| 0004 | 16 | VD | 24-0 | 26-15-11 | D01902 | = 1 | | | D01908 | = 1 | | | 115-199 | | |
| 0004R | 16 | TJ | 23-0 | 26-15-11 | D01902 | = 1 | | | D01908 | = 1 | | | 010-099 | | |
| 0005 | 16 | VD | 24-0 | 26-15-11 | GD02630 | ST.. | E | | GD02638 | ST.. | E | | 001-009 | | |
| 0005 | 16 | VD | 23-0 | 26-15-11 | GD02630 | ST.. | E | | GD02638 | ST.. | E | | 115-199 | | |
| 0005R | 16 | TJ | 24-0 | 26-15-11 | GD02630 | ST.. | E | | GD02638 | ST.. | E | | 010-099 | | |
| W2827 | 286N2827 | VOR RIGHT ANTENNA | | | | | | | | | | | | | |
| 001CO | | AA | 0-0 | 34-51-21 | D00621 | = C1 | | | D40663P | = C1 | | | ALL | | |
| 001CX | 65 | AA | 44-2 | 34-51-21 | D00621 | = A1 | | | D40663P | = A1 | | | 001-099 | | |
| 001CX | BS | AA | 43-0 | 34-51-21 | D00621 | = A1 | | | D40663P | = A1 | | | 115-199 | | |
| W2828 | 286N2828 | APU F/W TO APU FIRE DET ELEMENT (LOOP B) | | | | | | | | | | | | | |
| 0001 | 16 | VD | 10-7 | 26-15-11 | D40318P | 4 | | | D01904 | = 1 | | | 001-009, 115-199 | | |
| 0001R | 16 | TJ | 11-0 | 26-15-11 | D40318P | 4 | | | D01904 | = 1 | | | 010-099 | | |
| 0002 | 16 | VD | 14-9 | 26-15-11 | D40318P | 6 | | | D01914 | = 1 | 16 | | 001-009 | | |
| 0002 | 16 | VD | 14-10 | 26-15-11 | D40318P | 6 | | | D01914 | = 1 | 16 | | 115-199 | | |
| 0002R | 16 | TJ | 15-0 | 26-15-11 | D40318P | 6 | | | D01914 | = 1 | | | 010-099 | | |
| 0003 | 16 | VD | 10-5 | 26-15-11 | D40318P | 2 | | | GD02618 | ST.. | E | | 001-009 | | |
| 0003 | 16 | VD | 10-7 | 26-15-11 | D40318P | 2 | | | GD02618 | ST.. | E | | 115-199 | | |
| 0003R | 16 | TJ | 11-0 | 26-15-11 | D40318P | 2 | | | GD02618 | ST.. | E | | 010-099 | | |
| 0004 | 16 | VD | 10-11 | 26-15-11 | D01906 | = 1 | 16 | | D01912 | = 1 | 16 | | 001-009 | | |
| 0004 | 16 | VD | 15-2 | 26-15-11 | D01906 | = 1 | | | D01912 | = 1 | | | 115-199 | | |
| 0004R | 16 | TJ | 12-0 | 26-15-11 | D01906 | = 1 | 16 | | D01912 | = 1 | 16 | | 010-099 | | |

WIRE LIST

D280N032

91-21-11

Section W2820

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2828 | 286N2828 | | | | APU F/W TO APU FIRE DET ELEMENT (LOOP B) (continued) | | | | | | | | | | | |
| 0005 | 16 | | VD | | 11-2 | 26-15-11 | GD02636 | ST.. | E | | GD02640 | ST.. | E | | 001-009, 115-199 | |
| 0005R | 16 | | TJ | | 12-0 | 26-15-11 | GD02636 | ST.. | E | | GD02640 | ST.. | E | | 010-099 | |

WIRE LIST
D280N032

91-21-11
Section W2820
Page 4 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W2831 | 286N2831 | | | VIDEO COAX M10684 INTERFACE BOX TO VIDEO MONITOR | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-32-01 | D01287 | = C1 | | | D01283 | = C1 | | | ALL |
| 001CX | | 59 | | AA | 28-6 | 23-32-01 | D01287 | = A1 | | | D01283 | = A1 | | | 001-099 |
| 001CX | | 59 | | AA | 5-0 | 23-32-01 | D01287 | = A1 | | | D01283 | = A1 | | | 115-199 |
| W2833 | 286N2833 | | | VIDEO COAX M10684 INTERFACE BOX TO VIDEO MONITOR | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-32-01 | D01295 | = C1 | | | D01301 | = C1 | | | ALL |
| 001CX | | 59 | | AA | 40-4 | 23-32-01 | D01295 | = A1 | | | D01301 | = A1 | | | 001-099 |
| 001CX | | 66 | | AA | 25-0 | 23-32-01 | D01295 | = A1 | | | D01301 | = A1 | | | 115-199 |
| W2835 | 286N2835 | | | VIDEO COAX M10685 INTERFACE BOX TO VIDEO MONITOR | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-32-01 | D01317 | = C1 | | | D01329 | = C1 | | | ALL |
| 001CX | | 59 | | AA | 25-10 | 23-32-01 | D01317 | = A1 | | | D01329 | = A1 | | | 001-099 |
| 001CX | | 66 | | AA | 27-1 | 23-32-01 | D01317 | = A1 | | | D01329 | = A1 | | | 115-199 |
| W2837 | 286N2837 | | | VIDEO COAX M10685 INTERFACE BOX TO VIDEO MONITOR | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-32-01 | D01321 | = C1 | | | D01333 | = C1 | | | ALL |
| 001CX | | 59 | | AA | 11-11 | 23-32-01 | D01321 | = A1 | | | D01333 | = A1 | | | 001-099 |
| 001CX | | 66 | | AA | 5-9 | 23-32-01 | D01321 | = A1 | | | D01333 | = A1 | | | 115-199 |
| W2839 | 286N2839 | | | VIDEO COAX M10685 INTERFACE BOX TO VIDEO MONITOR | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-32-01 | D01325 | = C1 | | | D01337 | = C1 | | | ALL |
| 001CX | | 59 | | AA | 20-11 | 23-32-01 | D01325 | = A1 | | | D01337 | = A1 | | | 001-099 |
| 001CX | | 66 | | AA | 17-6 | 23-32-01 | D01325 | = A1 | | | D01337 | = A1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2830

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2843 | 286N2843 | | | VIDEO-SYSTEM | | | | | | | | | | | |
| 0001 | 20 | | GA | | 114-0 | 23-32-01 | D01273 | | A | | SP26001 | | 9 | | 001-099 |
| 0001 | 20 | | GA | | 122-0 | 23-32-01 | D01273 | | A | | SP26001 | | 9 | | 115-199 |
| 0002 | 20 | | GA | | 111-0 | 23-32-01 | D01273 | | F | | SP26005 | | 9 | | 001-099 |
| 0002 | 20 | | GA | | 112-0 | 23-32-01 | D01273 | | F | | SP26005 | | 9 | | 115-199 |
| 0003 | 22 | | GA | | 107-0 | 23-32-01 | D01273 | | K | | D01853 | | 6 | | 001-099 |
| 0003 | 22 | | GA | | 109-0 | 23-32-01 | D01273 | | K | | D01303 | | 6 | | 115-199 |
| 0004 | 22 | | GA | | 107-0 | 23-32-01 | D01273 | | L | | D01853 | | 8 | | 001-099 |
| 0004 | 22 | | GA | | 109-0 | 23-32-01 | D01273 | | L | | D01303 | | 8 | | 115-199 |
| 0005 | 22 | | GA | | 107-0 | 23-32-01 | D01273 | | CC | | D01853 | | 7 | | 001-099 |
| 0005 | 22 | | GA | | 109-0 | 23-32-01 | D01273 | | CC | | D01303 | | 7 | | 115-199 |
| 0006 | 20 | | GA | | 33-0 | 23-32-01 | SP26007 | | | 9 | D01853 | | 1 | | 001-099 |
| 0006 | 20 | | GA | | 31-0 | 23-32-01 | SP26007 | | | 9 | D01303 | | 1 | | 115-199 |
| 0007 | 20 | | GA | | 35-0 | 23-32-01 | SP26001 | | | 9 | D01853 | | 2 | | 001-099 |
| 0007 | 20 | | GA | | 40-0 | 23-32-01 | SP26001 | | | 9 | D01303 | | 2 | | 115-199 |
| 0008 | 20 | | GA | | 7-0 | 23-32-01 | GD02771 | | DC.. | E | D01853 | | 3 | | 001-099 |
| 0008 | 20 | | GA | | 2-0 | 23-32-01 | GD02993 | | DC.. | E | D01303 | | 3 | | 115-199 |
| 0009 | 20 | | GA | | 7-0 | 23-32-01 | GD02771 | | DC.. | E | D01853 | | 5 | | 001-099 |
| 0009 | 20 | | GA | | 2-0 | 23-32-01 | GD02993 | | DC.. | E | D01303 | | 5 | | 115-199 |
| 0010 | 20 | | GA | | 7-0 | 23-32-01 | GD02769 | | AC.. | E | D01853 | | 4 | | 001-099 |
| 0010 | 20 | | GA | | 2-0 | 23-32-01 | GD02995 | | AC.. | E | D01303 | | 4 | | 115-199 |
| 0011 | 22 | | GA | | 96-0 | 23-32-01 | D01273 | | S | | D01307 | | 6 | | 001-099 |
| 0011 | 22 | | GA | | 91-0 | 23-32-01 | D01273 | | S | | D01307 | | 6 | | 115-199 |
| 0012 | 22 | | GA | | 96-0 | 23-32-01 | D01273 | | F- | | D01307 | | 8 | | 001-099 |
| 0012 | 22 | | GA | | 91-0 | 23-32-01 | D01273 | | F- | | D01307 | | 8 | | 115-199 |
| 0013 | 22 | | GA | | 96-0 | 23-32-01 | D01273 | | X- | | D01307 | | 7 | | 001-099 |
| 0013 | 22 | | GA | | 91-0 | 23-32-01 | D01273 | | X- | | D01307 | | 7 | | 115-199 |
| 0014 | 20 | | GA | | 24-0 | 23-32-01 | SP26007 | | | 9 | D01307 | | 1 | | 001-099 |
| 0014 | 20 | | GA | | 30-0 | 23-32-01 | SP26007 | | | 9 | D01307 | | 1 | | 115-199 |
| 0015 | 20 | | GA | | 26-0 | 23-32-01 | SP26001 | | | 9 | D01307 | | 2 | | 001-099 |
| 0015 | 20 | | GA | | 39-0 | 23-32-01 | SP26001 | | | 9 | D01307 | | 2 | | 115-199 |
| 0016 | 20 | | GA | | 10-0 | 23-32-01 | GD03976 | | DC.. | E | D01307 | | 3 | | 001-099 |
| 0016 | 20 | | GA | | 7-0 | 23-32-01 | GD02759 | | DC.. | E | D01307 | | 3 | | 115-199 |
| 0017 | 20 | | GA | | 10-0 | 23-32-01 | GD03976 | | DC.. | E | D01307 | | 5 | | 001-099 |
| 0017 | 20 | | GA | | 7-0 | 23-32-01 | GD02759 | | DC.. | E | D01307 | | 5 | | 115-199 |
| 0018 | 20 | | GA | | 8-0 | 23-32-01 | GD03662 | | AC.. | E | D01307 | | 4 | | 001-099 |
| 0018 | 20 | | GA | | 7-0 | 23-32-01 | GD02763 | | AC.. | E | D01307 | | 4 | | 115-199 |
| 0019 | 20 | | GA | | 89-0 | 23-32-01 | D01311 | | 1 | | SP26003 | | 9 | | 001-099 |
| 0019 | 20 | | GA | | 91-0 | 23-32-01 | D01311 | | 1 | | SP26003 | | 9 | | 115-199 |
| 0020 | 20 | | GA | | 92-0 | 23-32-01 | D01311 | | 2 | | SP26001 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2840

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2843 | | 286N2843 | | | | VIDEO-SYSTEM (continued) | | | | | | | | | |
| 0020 | 20 | GA | | | 100-0 | 23-32-01 | D01311 | | 2 | | SP26001 | | 9 | | 115-199 |
| 0021 | 20 | GA | | | 9-0 | 23-32-01 | D01311 | | 3 | | GD03299 | DC.. | E | | 001-099 |
| 0021 | 20 | GA | | | 7-0 | 23-32-01 | D01311 | | 3 | | GD02765 | DC.. | E | | 115-199 |
| 0022 | 20 | GA | | | 9-0 | 23-32-01 | D01311 | | 4 | | GD03301 | AC.. | E | | 001-099 |
| 0022 | 20 | GA | | | 7-0 | 23-32-01 | D01311 | | 4 | | GD02767 | AC.. | E | | 115-199 |
| 0023 | 20 | GA | | | 9-0 | 23-32-01 | D01311 | | 5 | | GD03299 | DC.. | E | | 001-099 |
| 0023 | 20 | GA | | | 7-0 | 23-32-01 | D01311 | | 5 | | GD02765 | DC.. | E | | 115-199 |
| 0024 | 22 | GA | | | 31-0 | 23-32-01 | D01273 | | C | | D01311 | | 6 | | 001-099 |
| 0024 | 22 | GA | | | 30-0 | 23-32-01 | D01273 | | C | | D01311 | | 6 | | 115-199 |
| 0025 | 22 | GA | | | 31-0 | 23-32-01 | D01273 | | U- | | D01311 | | 7 | | 001-099 |
| 0025 | 22 | GA | | | 30-0 | 23-32-01 | D01273 | | U- | | D01311 | | 7 | | 115-199 |
| 0026 | 22 | GA | | | 31-0 | 23-32-01 | D01273 | | P- | | D01311 | | 8 | | 001-099 |
| 0026 | 22 | GA | | | 30-0 | 23-32-01 | D01273 | | P- | | D01311 | | 8 | | 115-199 |
| 0027 | 20 | GA | | | 29-0 | 23-32-01 | SP26007 | | | 9 | D01291 | | 1 | | 001-099 |
| 0027 | 20 | GA | | | 43-0 | 23-32-01 | SP26007 | | | 9 | D01291 | | 1 | | 115-199 |
| 0028 | 20 | GA | | | 32-0 | 23-32-01 | SP26001 | | | 9 | D01291 | | 2 | | 001-099 |
| 0028 | 20 | GA | | | 53-0 | 23-32-01 | SP26001 | | | 9 | D01291 | | 2 | | 115-199 |
| 0029 | 22 | GA | | | 103-0 | 23-32-01 | D01273 | | M | | D01291 | | 6 | | 001-099 |
| 0029 | 22 | GA | | | 77-0 | 23-32-01 | D01273 | | M | | D01291 | | 6 | | 115-199 |
| 0030 | 22 | GA | | | 103-0 | 23-32-01 | D01273 | | N | | D01291 | | 8 | | 001-099 |
| 0030 | 22 | GA | | | 77-0 | 23-32-01 | D01273 | | N | | D01291 | | 8 | | 115-199 |
| 0031 | 22 | GA | | | 103-0 | 23-32-01 | D01273 | | Y- | | D01291 | | 7 | | 001-099 |
| 0031 | 22 | GA | | | 77-0 | 23-32-01 | D01273 | | Y- | | D01291 | | 7 | | 115-199 |
| 0032 | 20 | GA | | | 7-0 | 23-32-01 | GD03795 | AC.. | E | | D01291 | | 4 | | 001-099 |
| 0032 | 20 | GA | | | 7-0 | 23-32-01 | GD02997 | AC.. | E | | D01291 | | 4 | | 115-199 |
| 0033 | 20 | GA | | | 7-0 | 23-32-01 | GD03797 | DC.. | E | | D01291 | | 5 | | 001-099 |
| 0033 | 20 | GA | | | 7-0 | 23-32-01 | GD02999 | DC.. | E | | D01291 | | 5 | | 115-199 |
| 0034 | 20 | GA | | | 7-0 | 23-32-01 | GD03797 | DC.. | E | | D01291 | | 3 | | 001-099 |
| 0034 | 20 | GA | | | 7-0 | 23-32-01 | GD02999 | DC.. | E | | D01291 | | 3 | | 115-199 |
| 0035 | 22 | GA | | | 109-0 | 23-32-02 | D01273 | | A- | | D41513P | | 6 | | 001-099 |
| 0035 | 22 | GA | | | 112-0 | 23-32-02 | D01273 | | A- | | D41513P | | 6 | | 115-199 |
| 0036 | 22 | GA | | | 109-0 | 23-32-02 | D01273 | | G | | D41513P | | 7 | | 001-099 |
| 0036 | 22 | GA | | | 112-0 | 23-32-02 | D01273 | | G | | D41513P | | 7 | | 115-199 |
| 0037 | 22 | GA | | | 109-0 | 23-32-02 | D01273 | | KK | | D41513P | | 8 | | 001-099 |
| 0037 | 22 | GA | | | 112-0 | 23-32-02 | D01273 | | KK | | D41513P | | 8 | | 115-199 |
| 0038 | 22 | GA | | | 109-0 | 23-32-02 | D01273 | | D- | | D41513P | | 3 | | 001-099 |
| 0038 | 22 | GA | | | 112-0 | 23-32-02 | D01273 | | D- | | D41513P | | 3 | | 115-199 |
| 0039 | 20 | GA | | | 3-0 | 23-32-02 | D01273 | | B | | GD03331 | DC.. | E | | 001-099 |
| 0039 | 20 | GA | | | 5-0 | 23-32-02 | D01273 | | B | | GD03331 | DC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2840

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2843 | 286N2843 | | | VIDEO-SYSTEM (continued) | | | | | | | | | | | |
| 0040 | 20 | | GA | | 3-0 | 23-32-02 | D01273 | | E | | GD03333 | AC.. | E | | 001-099 |
| 0040 | 20 | | GA | | 5-0 | 23-32-02 | D01273 | | E | | GD03333 | AC.. | E | | 115-199 |
| 0056 | 20 | | GA | | 3-0 | 23-32-02 | D01273 | | T | | GD03331 | DC.. | E | | 001-099 |
| 2001B | 22 | | GB | AA | 109-0 | 23-31-19 | D01273 | | C- | | D41513P | | 2 | | 001-099 |
| 2001B | 22 | | GB | AA | 112-0 | 23-32-02 | D01273 | | C- | | D41513P | | 2 | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 23-31-19 | D01273 | | B- | | D41513P | | 1 | | 001-099 |
| 2001R | 22 | | GB | AA | 0-0 | 23-32-02 | D01273 | | B- | | D41513P | | 1 | | 115-199 |
| 2002B | 22 | | GB | AB | 109-0 | 23-32-02 | D01273 | | H | | D41513P | | 5 | | 001-099 |
| 2002B | 22 | | GB | AB | 112-0 | 23-32-02 | D01273 | | H | | D41513P | | 5 | | 115-199 |
| 2002R | 22 | | GB | AB | 0-0 | 23-32-02 | D01273 | | J | | D41513P | | 4 | | ALL |
| 2003B | 22 | | GB | AC | 110-0 | 23-32-02 | D01273 | | W | | D41515J | | 2 | | 001-099 |
| 2003B | 22 | | GB | AC | 112-0 | 23-32-02 | D01273 | | W | | D41515J | | 2 | | 115-199 |
| 2003R | 22 | | GB | AC | 0-0 | 23-32-02 | D01273 | | X | | D41515J | | 1 | | ALL |
| 2004B | 22 | | GB | AD | 110-0 | 23-32-02 | D01273 | | P | | D41515J | | 4 | | 001-099 |
| 2004B | 22 | | GB | AD | 112-0 | 23-32-02 | D01273 | | P | | D41515J | | 4 | | 115-199 |
| 2004R | 22 | | GB | AD | 0-0 | 23-32-02 | D01273 | | R | | D41515J | | 3 | | ALL |
| W2849 | 286N2849 | | | M10684 JUNCTION BOX TO VIDEO MONITOR | | | | | | | | | | | |
| 0001 | 22 | | GA | | 26-0 | 23-32-01 | D01297 | | K | | D01299 | | 1 | | 115-199 |
| 0002 | 22 | | GA | | 26-0 | 23-32-01 | D01297 | | M | | D01299 | | 2 | | 115-199 |
| 0003 | 22 | | GA | | 7-0 | 23-32-01 | GD03309 | | DC.. | E | D01299 | | 3 | | 115-199 |
| 0004 | 22 | | GA | | 26-0 | 23-32-01 | D01297 | | L | | D01299 | | 4 | | 115-199 |
| 0005 | 22 | | GA | | 26-0 | 23-32-01 | D01297 | | J | | D01299 | | 5 | | 115-199 |
| 0006 | 22 | | GA | | 26-0 | 23-32-01 | D01297 | | H | | D01299 | | 6 | | 115-199 |
| 0007 | 22 | | GA | | 26-0 | 23-32-01 | D01297 | | E | | D01299 | | 7 | | 115-199 |
| 0008 | 22 | | GA | | 26-0 | 23-32-01 | D01297 | | F | | D01299 | | 8 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2840

Page 3 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|--|-----------------|----|----|---|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2853 | | 286N2853 | | | M10685 AFT INTERFACE BOX TO VIDEO MONITOR NO.6 | | | | | | | | | | | |
| 0001 | | 22 | | GA | | 24-0 | 23-32-01 | D01315 | | K | | D01859 | | 1 | | 001-099 |
| 0001 | | 22 | | GA | | 26-0 | 23-32-01 | D01315 | | K | | D01327 | | 1 | | 115-199 |
| 0002 | | 22 | | GA | | 24-0 | 23-32-01 | D01315 | | M | | D01859 | | 2 | | 001-099 |
| 0002 | | 22 | | GA | | 26-0 | 23-32-01 | D01315 | | M | | D01327 | | 2 | | 115-199 |
| 0003 | | 22 | | GA | | 8-0 | 23-32-01 | GD02765 | | DC.. | E | D01859 | | 3 | | 001-099 |
| 0003 | | 22 | | GA | | 6-0 | 23-32-01 | GD03335 | | DC.. | E | D01327 | | 3 | | 115-199 |
| 0004 | | 22 | | GA | | 24-0 | 23-32-01 | D01315 | | L | | D01859 | | 4 | | 001-099 |
| 0004 | | 22 | | GA | | 26-0 | 23-32-01 | D01315 | | L | | D01327 | | 4 | | 115-199 |
| 0005 | | 22 | | GA | | 24-0 | 23-32-01 | D01315 | | J | | D01859 | | 5 | | 001-099 |
| 0005 | | 22 | | GA | | 26-0 | 23-32-01 | D01315 | | J | | D01327 | | 5 | | 115-199 |
| 0006 | | 22 | | GA | | 24-0 | 23-32-01 | D01315 | | H | | D01859 | | 6 | | 001-099 |
| 0006 | | 22 | | GA | | 26-0 | 23-32-01 | D01315 | | H | | D01327 | | 6 | | 115-199 |
| 0007 | | 22 | | GA | | 24-0 | 23-32-01 | D01315 | | E | | D01859 | | 7 | | 001-099 |
| 0007 | | 22 | | GA | | 26-0 | 23-32-01 | D01315 | | E | | D01327 | | 7 | | 115-199 |
| 0008 | | 22 | | GA | | 24-0 | 23-32-01 | D01315 | | F | | D01859 | | 8 | | 001-099 |
| 0008 | | 22 | | GA | | 26-0 | 23-32-01 | D01315 | | F | | D01327 | | 8 | | 115-199 |
| W2857 | | 286N2857 | | | M10685 INTERFACE BOX TO VIDEO MONITOR | | | | | | | | | | | |
| 0001 | | 22 | | GA | | 22-0 | 23-32-01 | D01323 | | K | | D01869 | | 1 | | 001-099 |
| 0001 | | 22 | | GA | | 19-0 | 23-32-01 | D01323 | | K | | D01335 | | 1 | | 115-199 |
| 0002 | | 22 | | GA | | 22-0 | 23-32-01 | D01323 | | M | | D01869 | | 2 | | 001-099 |
| 0002 | | 22 | | GA | | 19-0 | 23-32-01 | D01323 | | M | | D01335 | | 2 | | 115-199 |
| 0003 | | 22 | | GA | | 8-0 | 23-32-01 | GD03329 | | DC.. | E | D01869 | | 3 | | 001-099 |
| 0003 | | 22 | | GA | | 7-0 | 23-32-01 | GD03329 | | DC.. | E | D01335 | | 3 | | 115-199 |
| 0004 | | 22 | | GA | | 22-0 | 23-32-01 | D01323 | | L | | D01869 | | 4 | | 001-099 |
| 0004 | | 22 | | GA | | 19-0 | 23-32-01 | D01323 | | L | | D01335 | | 4 | | 115-199 |
| 0005 | | 22 | | GA | | 22-0 | 23-32-01 | D01323 | | J | | D01869 | | 5 | | 001-099 |
| 0005 | | 22 | | GA | | 19-0 | 23-32-01 | D01323 | | J | | D01335 | | 5 | | 115-199 |
| 0006 | | 22 | | GA | | 22-0 | 23-32-01 | D01323 | | H | | D01869 | | 6 | | 001-099 |
| 0006 | | 22 | | GA | | 19-0 | 23-32-01 | D01323 | | H | | D01335 | | 6 | | 115-199 |
| 0007 | | 22 | | GA | | 22-0 | 23-32-01 | D01323 | | E | | D01869 | | 7 | | 001-099 |
| 0007 | | 22 | | GA | | 19-0 | 23-32-01 | D01323 | | E | | D01335 | | 7 | | 115-199 |
| 0008 | | 22 | | GA | | 22-0 | 23-32-01 | D01323 | | F | | D01869 | | 8 | | 001-099 |
| 0008 | | 22 | | GA | | 19-0 | 23-32-01 | D01323 | | F | | D01335 | | 8 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W2850

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W2865 | 286N2865 | | | M10684 JUNCTION BOX TO VIDEO MONITOR NO.3 | | | | | | | | | | | |
| 0001 | 22 | | GA | | 30-0 | 23-32-01 | D00947 | | K | | D01863 | 1 | | | 001-099 |
| 0002 | 22 | | GA | | 30-0 | 23-32-01 | D00947 | | M | | D01863 | 2 | | | 001-099 |
| 0003 | 22 | | GA | | 10-0 | 23-32-01 | GD03779 | | DC.. | E | D01863 | 3 | | | 001-099 |
| 0004 | 22 | | GA | | 30-0 | 23-32-01 | D00947 | | L | | D01863 | 4 | | | 001-099 |
| 0005 | 22 | | GA | | 30-0 | 23-32-01 | D00947 | | J | | D01863 | 5 | | | 001-099 |
| 0006 | 22 | | GA | | 30-0 | 23-32-01 | D00947 | | H | | D01863 | 6 | | | 001-099 |
| 0007 | 22 | | GA | | 30-0 | 23-32-01 | D00947 | | E | | D01863 | 7 | | | 001-099 |
| 0008 | 22 | | GA | | 30-0 | 23-32-01 | D00947 | | F | | D01863 | 8 | | | 001-099 |
| W2867 | 286N2867 | | | M10684 FWD INTERFACE BOX TO MONITOR NO.5 | | | | | | | | | | | |
| 0001 | 22 | | GA | | 55-0 | 23-32-01 | D00951 | | K | | D01857 | 1 | | | 001-099 |
| 0002 | 22 | | GA | | 55-0 | 23-32-01 | D00951 | | M | | D01857 | 2 | | | 001-099 |
| 0003 | 22 | | GA | | 7-0 | 23-32-01 | GD03309 | | DC.. | E | D01857 | 3 | | | 001-099 |
| 0004 | 22 | | GA | | 55-0 | 23-32-01 | D00951 | | L | | D01857 | 4 | | | 001-099 |
| 0005 | 22 | | GA | | 55-0 | 23-32-01 | D00951 | | J | | D01857 | 5 | | | 001-099 |
| 0006 | 22 | | GA | | 55-0 | 23-32-01 | D00951 | | H | | D01857 | 6 | | | 001-099 |
| 0007 | 22 | | GA | | 55-0 | 23-32-01 | D00951 | | E | | D01857 | 7 | | | 001-099 |
| 0008 | 22 | | GA | | 55-0 | 23-32-01 | D00951 | | F | | D01857 | 8 | | | 001-099 |
| W2869 | 286N2869 | | | VIDEO COAX M10684 INTERFACE BOX TO VIDEO MONITOR NO.5 | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-32-01 | D00953 | | = C1 | | D00955 | = C1 | | | 001-099 |
| 001CX | | 59 | | AA | 53-8 | 23-32-01 | D00953 | | = A1 | | D00955 | = A1 | | | 001-099 |

WIRE LIST

D280N032

91-21-11
Section W2860
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|--------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W2883 | 286N2883 | | | | M10685 INTERFACE BOX AFT TO VIDEO MONITOR NO.7 | | | | | | | | | | | |
| 0001 | 22 | | GA | | 12-0 | 23-32-01 | D01893 | | K | | | D01861 | | 1 | | 001-099 |
| 0002 | 22 | | GA | | 12-0 | 23-32-01 | D01893 | | M | | | D01861 | | 2 | | 001-099 |
| 0003 | 22 | | GA | | 8-0 | 23-32-01 | GD03299 | | DC.. | E | | D01861 | | 3 | | 001-099 |
| 0004 | 22 | | GA | | 12-0 | 23-32-01 | D01893 | | L | | | D01861 | | 4 | | 001-099 |
| 0005 | 22 | | GA | | 12-0 | 23-32-01 | D01893 | | J | | | D01861 | | 5 | | 001-099 |
| 0006 | 22 | | GA | | 12-0 | 23-32-01 | D01893 | | H | | | D01861 | | 6 | | 001-099 |
| 0007 | 22 | | GA | | 12-0 | 23-32-01 | D01893 | | E | | | D01861 | | 7 | | 001-099 |
| 0008 | 22 | | GA | | 12-0 | 23-32-01 | D01893 | | F | | | D01861 | | 8 | | 001-099 |
| W2885 | 286N2885 | | | | M10685 FWD INTERFACE BOX TO VIDEO MONITOR NO.4 | | | | | | | | | | | |
| 0001 | 22 | | GA | | 41-0 | 23-32-01 | D01891 | | K | | | D01865 | | 1 | | 001-099 |
| 0002 | 22 | | GA | | 41-0 | 23-32-01 | D01891 | | M | | | D01865 | | 2 | | 001-099 |
| 0003 | 22 | | GA | | 10-0 | 23-32-01 | GD03783 | | DC.. | E | | D01865 | | 3 | | 001-099 |
| 0004 | 22 | | GA | | 41-0 | 23-32-01 | D01891 | | L | | | D01865 | | 4 | | 001-099 |
| 0005 | 22 | | GA | | 41-0 | 23-32-01 | D01891 | | J | | | D01865 | | 5 | | 001-099 |
| 0006 | 22 | | GA | | 41-0 | 23-32-01 | D01891 | | H | | | D01865 | | 6 | | 001-099 |
| 0007 | 22 | | GA | | 41-0 | 23-32-01 | D01891 | | E | | | D01865 | | 7 | | 001-099 |
| 0008 | 22 | | GA | | 41-0 | 23-32-01 | D01891 | | F | | | D01865 | | 8 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W2880

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|--------|------|------|--------|---------|------|-------------|------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W3000 | 286N3000 | | | | MN LNDG GEAR FWD JCTN BOX TO BRAKE TEMP SENSOR - LEFT | | | | | | | | | | |
| 4501G | 18 | | UY | TA | 4-0 | 32-46-11 | D02648 | 3 | 4H | | TB0209K | A002 | 1 | | 115-199 |
| 4501W | 18 | | UY | TA | 0-0 | 32-46-11 | D02648 | 1 | 4L | | TB0209K | E002 | 1 | | 115-199 |
| W3002 | 286N3002 | | | | MN LNDG GEAR AFT JCTN BOX TO BRAKE TEMP SENSOR - LEFT | | | | | | | | | | |
| 4501G | 18 | | UY | TA | 4-0 | 32-46-11 | D02652 | 3 | 4H | | TB0210K | C001 | 1 | | 115-199 |
| 4501W | 18 | | UY | TA | 0-0 | 32-46-11 | D02652 | 1 | 4L | | TB0210K | A001 | 1 | | 115-199 |
| W3004 | 286N3004 | | | | MN LNDG GEAR FWD JCTN BOX TO ANTI-SKID SENSORS - LEFT | | | | | | | | | | |
| 2501B | 20 | | HQ | AA | 3-10 | 32-42-11 | D02048 | 3 | | | TB0209K | A003 | 1 | | ALL |
| 2501R | 20 | | HQ | AA | 0-0 | 32-42-11 | D02048 | 1 | | | TB0209K | C003 | 1 | | ALL |
| 2501Z | | | | AA | 0-0 | 32-42-11 | D02048 | DED | | | TB0209L | A004 | 1 | | ALL |
| 2502B | 20 | | HQ | AB | 3-10 | 32-42-11 | D02050 | 3 | | | TB0209K | E003 | 1 | | ALL |
| 2502R | 20 | | HQ | AB | 0-0 | 32-42-11 | D02050 | 1 | | | TB0209K | G003 | 1 | | ALL |
| 2502Z | | | | AB | 0-0 | 32-42-11 | D02050 | DED | | | TB0209L | E004 | 1 | | ALL |
| W3006 | 286N3006 | | | | MN LNDG GEAR FWD JCTN BOX TO SYS 1 TRUCK TILT PROX SENSORS - LEFT | | | | | | | | | | |
| A-AA | | | | | 0-0 | 32-09-11 | S10062 | BLU | | | TB0209K | G001 | 1 | | ALL |
| A-AB | | | | | 0-0 | 32-09-11 | S10062 | RED | | | TB0209K | E001 | 1 | | ALL |

WIRE LIST

D280N032

91-21-11
Section W3000
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3010 | 286N3010 | | | MN LNDG GEAR - WING/TRUCK DISC TO FWD JCTN BOX - LEFT | | | | | | | | | | | |
| 2001B | 18 | HM | CC | 17-0 | 32-09-11 | D40082P | | 12 | | | TB0209K | G001 | 1 | | 001-099 |
| 2001B | 18 | HM | CC | 20-1 | 32-09-11 | D40082P | | 12 | | | TB0209K | G001 | 1 | | 115-199 |
| 2001R | 18 | HM | CC | 0-0 | 32-09-11 | D40082P | | 11 | | | TB0209K | E001 | 1 | | ALL |
| 2501B | 20 | HQ | AA | 17-0 | 32-42-11 | D40082P | | 9 | | | TB0209K | A003 | 1 | | 001-099 |
| 2501B | 20 | HQ | AA | 20-0 | 32-42-11 | D40082P | | 9 | | | TB0209K | A003 | 1 | | 115-199 |
| 2501R | 20 | HQ | AA | 0-0 | 32-42-11 | D40082P | | 10 | | | TB0209K | C003 | 1 | | ALL |
| 2501Z | | | AA | 0-0 | 32-42-11 | D40082P | | 7 | | | TB0209L | A004 | 1 | | ALL |
| 2502B | 20 | HQ | AB | 17-0 | 32-42-11 | D40082P | | 3 | | | TB0209K | E003 | 1 | | 001-099 |
| 2502B | 20 | HQ | AB | 20-0 | 32-42-11 | D40082P | | 3 | | | TB0209K | E003 | 1 | | 115-199 |
| 2502R | 20 | HQ | AB | 0-0 | 32-42-11 | D40082P | | 4 | | | TB0209K | G003 | 1 | | ALL |
| 2502Z | | | AB | 0-0 | 32-42-11 | D40082P | | 5 | | | TB0209L | E004 | 1 | | ALL |
| 4501G | 18 | UY | TA | 20-0 | 32-46-11 | D40082P | | 13 | 4G | | TB0209K | A002 | 1 | | 115-199 |
| 4501W | 18 | UY | TA | 0-0 | 32-46-11 | D40082P | | 14 | 4K | | TB0209K | E002 | 1 | | 115-199 |
| 4502G | 18 | UY | TB | 20-0 | 32-46-11 | D40082P | | 1 | 4G | | TB0209K | A001 | 1 | | 115-199 |
| 4502W | 18 | UY | TB | 0-0 | 32-46-11 | D40082P | | 2 | 4K | | TB0209K | C001 | 1 | | 115-199 |
| W3012 | 286N3012 | | | MN LNDG GEAR - WING/TRUCK DISC TO AFT JCTN BOX - LEFT | | | | | | | | | | | |
| 2001B | 18 | HM | CC | 20-0 | 32-09-12 | D40084P | | 12 | | | TB0210K | G001 | 1 | | ALL |
| 2001R | 18 | HM | CC | 0-0 | 32-09-12 | D40084P | | 11 | | | TB0210K | E001 | 1 | | ALL |
| 2501B | 20 | HQ | AA | 20-0 | 32-42-11 | D40084P | | 9 | | | TB0210K | E003 | 1 | | ALL |
| 2501R | 20 | HQ | AA | 0-0 | 32-42-11 | D40084P | | 10 | | | TB0210K | G003 | 1 | | ALL |
| 2501Z | | | AA | 0-0 | 32-42-11 | D40084P | | 7 | | | TB0210L | A004 | 1 | | ALL |
| 2502B | 20 | HQ | AB | 20-0 | 32-42-11 | D40084P | | 3 | | | TB0210K | A003 | 1 | | ALL |
| 2502R | 20 | HQ | AB | 0-0 | 32-42-11 | D40084P | | 4 | | | TB0210K | C003 | 1 | | ALL |
| 2502Z | | | AB | 0-0 | 32-42-11 | D40084P | | 6 | | | TB0210L | E004 | 1 | | ALL |
| 4501G | 18 | UY | TA | 20-0 | 32-46-11 | D40084P | | 2 | 4G | | TB0210K | C001 | 1 | | 115-199 |
| 4501W | 18 | UY | TA | 0-0 | 32-46-11 | D40084P | | 1 | 4K | | TB0210K | A001 | 1 | | 115-199 |
| 4502G | 18 | UY | TB | 20-0 | 32-46-11 | D40084P | | 14 | 4G | | TB0210K | E002 | 1 | | 115-199 |
| 4502W | 18 | UY | TB | 0-0 | 32-46-11 | D40084P | | 13 | 4K | | TB0210K | A002 | 1 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3010

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|--------|------|------|--------|-------|---------|------|--------|-------------|-----|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3020 | 286N3020 | | | | MN LNDG GEAR - DOWN INDICATION PROX SENSORS SYS 1 - LEFT | | | | | | | | | | | | |
| A-AA | | | | | 5-0 | 32-61-22 | S10061 | | RED | | | D40380P | | 1 | | ALL | |
| A-AB | | | | | 5-0 | 32-61-22 | S10061 | | BLU | | | D40380P | | 2 | | ALL | |
| W3022 | 286N3022 | | | | MN LNDG GEAR - DOWN INDICATION PROX SENSORS SYS 2 - LEFT | | | | | | | | | | | | |
| A-AA | | | | | 0-0 | 32-61-22 | S10074 | | RED | | | D40382P | | 1 | | ALL | |
| A-AB | | | | | 0-0 | 32-61-22 | S10074 | | BLU | | | D40382P | | 2 | | ALL | |
| W3024 | 286N3024 | | | | MN LNDG GEAR AFT JCTN BOX TO ANTI-SKID SENSORS - LEFT | | | | | | | | | | | | |
| 2501B | 20 | HQ | AA | | 3-10 | 32-42-11 | D02052 | | 3 | | | TB0210K | E003 | 1 | | ALL | |
| 2501R | 20 | HQ | AA | | 0-0 | 32-42-11 | D02052 | | 1 | | | TB0210K | G003 | 1 | | ALL | |
| 2501Z | | | AA | | 0-0 | 32-42-11 | D02052 | | DED | | | TB0210L | A004 | 1 | | ALL | |
| 2502B | 20 | HQ | AB | | 3-10 | 32-42-11 | D02054 | | 3 | | | TB0210K | A003 | 1 | | ALL | |
| 2502R | 20 | HQ | AB | | 0-0 | 32-42-11 | D02054 | | 1 | | | TB0210K | C003 | 1 | | ALL | |
| 2502Z | | | AB | | 0-0 | 32-42-11 | D02054 | | DED | | | TB0210L | E004 | 1 | | ALL | |
| W3026 | 286N3026 | | | | MN LNDG GEAR AFT JCTN BOX TO SYS 2 TRUCK TILT PROX SENSORS - LEFT | | | | | | | | | | | | |
| A-AA | | | | | 0-0 | 32-09-12 | S10064 | | BLU | | | TB0210K | G001 | 1 | | ALL | |
| A-AB | | | | | 0-0 | 32-09-12 | S10064 | | RED | | | TB0210K | E001 | 1 | | ALL | |

WIRE LIST

D280N032

91-21-11
Section W3020
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3030 | 286N3030 | | | MN LNDG GEAR FWD JCTN BOX TO BRAKE TEMP SENSOR - LEFT | | | | | | | | | | | |
| 4501G | 18 | UY | TA | | 4-0 | 32-46-11 | D02650 | 3 | 4H | | TB0209K | A001 | 1 | | 115-199 |
| 4501W | 18 | UY | TA | | 0-0 | 32-46-11 | D02650 | 1 | 4L | | TB0209K | C001 | 1 | | 115-199 |
| W3032 | 286N3032 | | | MN LNDG GEAR AFT JCTN BOX TO BRAKE TEMP SENSORS - LEFT | | | | | | | | | | | |
| 4501G | 18 | UY | TA | | 4-0 | 32-46-11 | D02654 | 3 | 4H | | TB0210K | E002 | 1 | | 115-199 |
| 4501W | 18 | UY | TA | | 0-0 | 32-46-11 | D02654 | 1 | 4L | | TB0210K | A002 | 1 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3030

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|---------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3050 | 286N3050 | | | | NOSE GEAR DISC TO APU REMOTE CONT PNL | | | | | | | | | | | |
| 0001 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 1 | | | TB0225C | C001 | 1 | | 001-099 |
| 0001 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 1 | | | TB0025K | A007 | 1 | | 115-199 |
| 0002 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 24 | | | TB0025C | E007 | 1 | | 001-099 |
| 0002 | 20 | | HL | | 1-0 | 26-15-12 | TB0025L | A008 | 1 | | | TB0025K | C007 | 1 | | 115-199 |
| 0003 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 5 | | | TB0225C | E004 | 1 | | 001-099 |
| 0003 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 5 | | | TB0025L | A008 | 1 | | 115-199 |
| 0004 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 6 | | | TB0225C | A001 | 1 | | 001-099 |
| 0004 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 6 | | | TB0025K | E007 | 1 | | 115-199 |
| 0005 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 3 | | | TB0025C | A007 | 1 | | 001-099 |
| 0005 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 3 | | | TB0025K | E009 | 1 | | 115-199 |
| 0006 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 4 | | | TB0025K | C008 | 1 | | 001-099 |
| 0006 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 4 | | | TB0025K | A009 | 1 | | 115-199 |
| 0007 | 20 | | HL | | 8-0 | SPARE | D40162P | | 22 | | | TB0025K | G006 | 1 | | 001-099 |
| 0007 | 20 | | HL | | 8-0 | 32-12-12 | D40162P | | 7 | | | TB0025K | G007 | 1 | | 115-199 |
| 0008 | 20 | | HL | | 8-0 | SPARE | D40162P | | 8 | | | TB0225K | A003 | 1 | | 001-099 |
| 0008 | 20 | | HL | | 8-0 | 32-12-12 | D40162P | | 2 | | | TB0025K | C009 | 1 | | 115-199 |
| 0009 | 20 | | HL | | 8-0 | 26-22-21 | D40162P | | 9 | | | TB0025C | C007 | 1 | | 001-099 |
| 0009 | 20 | | HL | | 8-0 | 26-15-12 | D40162P | | 9 | | | TB0025K | G009 | 1 | | 115-199 |
| 0010 | 20 | | HL | | 8-0 | 32-44-11 | D40162P | | 10 | | | TB0025K | G001 | 1 | | 115-199 |
| 0011 | 20 | | HL | | 8-0 | 32-44-11 | D40162P | | 16 | | | TB0025K | G006 | 1 | | 115-199 |
| 0012 | 20 | | HL | | 8-0 | 32-44-11 | D40162P | | 22 | | | TB0025K | G010 | 1 | | 115-199 |
| 2501B | 20 | | HQ | AA | 8-0 | 23-71-11 | D40162P | | 11 | | | TB0025K | A010 | 1 | | 115-199 |
| 2501R | 20 | | HQ | AA | 0-0 | 23-71-11 | D40162P | | 12 | | | TB0025K | C010 | 1 | | 115-199 |
| 2501Z | | | | AA | 0-0 | 23-71-11 | D40162P | | 13 | | | TB0025K | E010 | 1 | | 115-199 |
| 2502B | 20 | | HQ | AB | 8-0 | 23-71-11 | D40162P | | 17 | | | TB0025K | A011 | 1 | | 115-199 |
| 2502R | 20 | | HQ | AB | 0-0 | 23-71-11 | D40162P | | 18 | | | TB0025K | C011 | 1 | | 115-199 |
| 2502Z | | | | AB | 0-0 | 23-71-11 | D40162P | | 19 | | | TB0025K | E011 | 1 | | 115-199 |
| 2503B | 20 | | HQ | AC | 8-0 | 32-12-12 | TB0025K | G008 | 1 | | | D40162P | | 7 | | 001-099 |
| 2503B | 20 | | HQ | AC | 4-0 | 32-12-12 | TB0025K | G007 | 1 | | | SP01180 | | 9 | | 115-199 |
| 2503R | 20 | | HQ | AC | 0-0 | 32-12-12 | TB0025K | E008 | 1 | | | D40162P | | 2 | | 001-099 |
| 2503R | 20 | | HQ | AC | 0-0 | 32-12-12 | TB0025K | C009 | 1 | | | SP01182 | | 9 | | 115-199 |
| 2503Z | | | | AC | 0-0 | 32-12-12 | TB0025K | DED | | | | D40162P | DED | | | 001-099 |
| 2503Z | | | | AC | 0-0 | 32-12-12 | TB0025K | DED | | | | SP01180 | DED | | | 115-199 |
| W3052 | 286N3052 | | | | P63 PNL. NOSE LANDING GEAR,LEFT | | | | | | | | | | | |
| 0001 | 18 | | HL | | 9-11 | 33-31-11 | D40388P | | D | | | S00324 | 2 | C | | 001-099 |
| 0001 | 18 | | HL | | 10-5 | 33-31-11 | D40388P | | D | | | S00324 | 2 | C | | 115-199 |
| 0002 | 18 | | HL | | 9-11 | 33-31-11 | D40388P | | C | | | S00324 | 3 | C | | 001-099 |
| 0002 | 18 | | HL | | 10-5 | 33-31-11 | D40388P | | C | | | S00324 | 3 | C | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3050

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|------------|--|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3052 | | 286N3052 | | | P63 PNL. NOSE LANDING GEAR,LEFT (continued) | | | | | | | | | | | |
| 0003 | | 12 | | HA | | 3-2 | 33-42-11 | D02308 | | 3 | | L00358 | =P | M | | ALL |
| 0004 | | 12 | | HA | | 3-1 | 33-42-11 | L00358 | =G | M | | TB0045B | A002 | 1C | | 001-099 |
| 0004 | | 12 | | HA | | 2-11 | 33-42-11 | L00358 | =G | M | | TB0045C | A003 | 1C | | 115-199 |
| 0005 | | 12 | | HA | | 8-9 | 33-42-11 | D40388P | | R | | TB0045B | A002 | 1C | | 001-099 |
| 0005 | | 12 | | HA | | 9-2 | 33-42-11 | D40388P | | R | | TB0045C | A003 | 1C | | 115-199 |
| 0006 | | 12 | | HA | | 10-1 | 33-42-11 | D02308 | | 2 | | D40388P | | P | | 001-099 |
| 0006 | | 12 | | HA | | 10-5 | 33-42-11 | D02308 | | 2 | | D40388P | | P | | 115-199 |
| 0007 | | 20 | | HL | | 10-1 | 33-42-11 | D02308 | | 7 | | D40388P | | H | | 001-099 |
| 0007 | | 20 | | HL | | 10-5 | 33-42-11 | D02308 | | 7 | | D40388P | | H | | 115-199 |
| 0008 | | 12 | | HA | | 2-6 | 33-42-11 | D02308 | | 8 | | TB0045B | A002 | 1C | | 001-099 |
| 0008 | | 12 | | HA | | 2-6 | 33-42-11 | D02308 | | 8 | | TB0045C | A003 | 1C | | 115-199 |
| 0010 | | 18 | | HL | | 3-5 | 33-42-21 | D00188 | | 3 | | L00079 | =P | M | | 001-099 |
| 0010 | | 18 | | HL | | 2-11 | 33-42-21 | D00188 | | 3 | | L00079 | =P | M | | 115-199 |
| 0011 | | 16 | | HL | | 4-0 | 33-42-21 | L00079 | =G | M | | TB0045C | A005 | 1 | | 001-099 |
| 0011 | | 16 | | HL | | 3-1 | 33-42-21 | L00079 | =G | M | | TB0045B | | 2 | 1 | 115-199 |
| 0012 | | 20 | | HL | | 9-9 | 33-42-21 | D00188 | | 7 | | D40388P | | B | | 001-099 |
| 0012 | | 20 | | HL | | 10-0 | 33-42-21 | D00188 | | 7 | | D40388P | | B | | 115-199 |
| 0013 | | 18 | | HL | | 2-6 | 33-42-21 | D00188 | | 2 | | TB0045D | A006 | 1 | | 001-099 |
| 0013 | | 18 | | HL | | 2-2 | 33-42-21 | D00188 | | 2 | | TB0045D | A006 | 1 | | 115-199 |
| 0014 | | 18 | | HL | | 2-6 | 33-42-21 | D00188 | | 8 | | TB0045C | A005 | 1 | | 001-099 |
| 0014 | | 18 | | HL | | 2-2 | 33-42-21 | D00188 | | 8 | | TB0045B | | 2 | 1 | 115-199 |
| 0015 | | 16 | | HL | | 9-1 | 33-42-21 | D40388P | | K | | TB0045C | A005 | 1 | | 001-099 |
| 0015 | | 16 | | HL | | 9-3 | 33-42-21 | D40388P | | K | | TB0045B | | 2 | 1 | 115-199 |
| 0017 | | 18 | | HL | | 9-1 | 33-42-21 | D40388P | | A | | TB0045D | A006 | 1 | | 001-099 |
| 0017 | | 18 | | HL | | 9-2 | 33-42-21 | D40388P | | A | | TB0045D | A006 | 1 | | 115-199 |
| 0025 | | 18 | | HL | | 9-11 | 32-12-12 | D40388P | | G | | S10193 | | 3 | C | 001-099 |
| 0025 | | 18 | | HL | | 10-3 | 32-12-12 | D40388P | | G | | S10193 | | 3 | C | 115-199 |
| 0026 | | 18 | | HL | | 9-11 | 32-12-12 | D40388P | | F | | S10193 | | 1 | C | 001-099 |
| 0026 | | 18 | | HL | | 10-3 | 32-12-12 | D40388P | | F | | S10193 | | 1 | C | 115-199 |
| 0027 | | 18 | | HL | | 9-11 | 32-12-12 | D40388P | | E | | S10193 | | 2 | C | 001-099 |
| 0027 | | 18 | | HL | | 10-3 | 32-12-12 | D40388P | | E | | S10193 | | 2 | C | 115-199 |
| 0030 | | 18 | | HL | | 10-6 | SPARE | D40388P | | O | | S10361 | CAP | Y | | 115-199 |
| 0031 | | 18 | | HL | | 10-6 | SPARE | D40388P | | N | | S10361 | CAP | Y | | 115-199 |
| 0040 | | 12 | | HA | | 3-1 | 33-42-12 | D02294 | | 3 | | L00359 | =P | M | | 001-099 |
| 0041 | | 12 | | HA | | 4-1 | 33-42-12 | L00359 | =G | M | | TB0045B | E002 | 1C | | 001-099 |
| 0042 | | 12 | | HA | | 2-10 | 33-42-12 | D02294 | | 8 | | TB0045B | E002 | 1C | | 001-099 |
| 0043 | | 12 | | HA | | 8-9 | 33-42-12 | D40388P | | S | | TB0045B | E002 | 1C | | 001-099 |
| 0044 | | 12 | | HA | | 10-5 | 33-42-12 | D02294 | | 2 | | D40388P | | T | | 001-099 |
| 0045 | | 18 | | HL | | 10-5 | 33-42-12 | D02294 | | 7 | | D40388P | | W | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3050

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3052 | 286N3052 | | | P63 PNL. NOSE LANDING GEAR,LEFT (continued) | | | | | | | | | | | |
| 0046 | 20 | | HL | | 9-6 | 33-42-31 | D40388P | | M | | D02198 | 7 | | | 001-099 |
| 0047 | 16 | | HA | | 9-8 | 33-42-31 | D02198 | | 3 | | L00395 | =P | M | | 001-099 |
| 0048 | 16 | | HA | | 2-4 | 33-42-31 | D02198 | | 8 | | TB0045C | A005 | 1 | | 001-099 |
| 0049 | 16 | | HA | | 2-4 | 33-42-31 | D02198 | | 2 | | TB0045D | A006 | 1 | | 001-099 |
| 0050 | 16 | | HA | | 9-2 | 33-42-31 | L00395 | =G | M | | TB0045C | A005 | 1 | | 001-099 |
| 2001B | 18 | | HM | AA | 8-9 | 32-09-11 | D40388P | | I | | TB0045A | A001 | 1 | | 001-099 |
| 2001B | 18 | | HM | AA | 9-1 | 32-09-11 | D40388P | | I | | TB0045A | A001 | 1 | | 115-199 |
| 2001R | 18 | | HM | AA | 0-0 | 32-09-11 | D40388P | | J | | TB0045A | C001 | 1 | | ALL |
| 2501B | 18 | | HQ | AB | 4-9 | 32-12-12 | S10361 | | NO | LW | TB0025K | G008 | 1 | | 001-099 |
| 2501B | 20 | | HQ | AB | 3-6 | 32-12-12 | S10361 | | NO | LW | SP01180 | | 9 | | 115-199 |
| 2501R | 18 | | HQ | AB | 0-0 | 32-12-12 | S10361 | | C | LW | TB0025K | E008 | 1 | | 001-099 |
| 2501R | 20 | | HQ | AB | 0-0 | 32-12-12 | S10361 | | C | LW | SP01182 | | 9 | | 115-199 |
| 2501Z | | | | AB | 0-0 | 32-12-12 | S10361 | | DED | | TB0025K | DED | | | 001-099 |
| 2501Z | | | | AB | 0-0 | 32-12-12 | S10361 | | DED | | SP01180 | DED | | | 115-199 |
| A-A | | | | | 0-0 | 32-09-11 | S10067 | | RED | | TB0045A | C001 | 1 | | ALL |
| A-B | | | | | 0-0 | 32-09-11 | S10067 | | BLU | | TB0045A | A001 | 1 | | ALL |
| W3054 | 286N3054 | | | P62 PNL. NOSE GEAR LANDING GEAR,RIGHT | | | | | | | | | | | |
| 0001 | 18 | | HL | | 8-9 | 23-43-11 | D40488P | | H | | S00426 | 1 | C | | 001-099 |
| 0001 | 18 | | HL | | 11-3 | 23-43-11 | D40488P | | H | | S00426 | 1 | C | | 115-199 |
| 0002 | 18 | | HL | | 8-9 | 23-43-11 | D40488P | | I | | S00426 | 2 | C | | 001-099 |
| 0002 | 18 | | HL | | 11-3 | 23-43-11 | D40488P | | I | | S00426 | 2 | C | | 115-199 |
| 0003 | 20 | | HL | | 9-0 | 33-51-11 | D40488P | | C | | S10035 | 11 | C | | 001-099 |
| 0003 | 20 | | HL | | 11-0 | 33-51-11 | D40488P | | C | | S10035 | 11 | C | | 115-199 |
| 0004 | 20 | | HL | | 9-0 | 33-51-11 | D40488P | | D | | S10035 | 8 | C | | 001-099 |
| 0004 | 20 | | HL | | 11-0 | 33-51-11 | D40488P | | D | | S10035 | 8 | C | | 115-199 |
| 0005 | 20 | | HL | | 9-0 | 33-51-11 | D40488P | | E | | S10035 | 5 | C | | 001-099 |
| 0005 | 20 | | HL | | 11-0 | 33-51-11 | D40488P | | E | | S10035 | 5 | C | | 115-199 |
| 0006 | 20 | | HL | | 9-0 | 33-51-11 | D40488P | | F | | S10035 | 2 | C | | 001-099 |
| 0006 | 20 | | HL | | 11-0 | 33-51-11 | D40488P | | F | | S10035 | 2 | C | | 115-199 |
| 0007 | 20 | | HL | | 1-0 | 33-51-11 | S10035 | | 1 | C | S10035 | 4 | C | * | ALL |
| 0008 | 20 | | HL | | 1-0 | 33-51-11 | S10035 | | 4 | C | S10035 | 7 | C | * | ALL |
| 0009 | 20 | | HL | | 1-1 | 33-51-11 | S10035 | | 7 | C | S10035 | 10 | C | * | 001-099 |
| 0009 | 20 | | HL | | 1-0 | 33-51-11 | S10035 | | 7 | C | S10035 | 10 | C | * | 115-199 |
| 0013 | 20 | | HL | | 9-0 | 33-51-11 | D40488P | | C- | | S10035 | 10 | C | * | 001-099 |
| 0013 | 20 | | HL | | 11-0 | 33-51-11 | D40488P | | C- | | S10035 | 10 | C | * | 115-199 |
| 0014 | 12 | | HA | | 2-11 | 33-42-12 | D02294 | | 3 | | L00359 | =P | M | | 115-199 |
| 0015 | 12 | | HA | | 3-1 | 33-42-12 | L00359 | =G | M | | TB0025B | A002 | 1C | | 115-199 |
| 0016 | 12 | | HA | | 2-7 | 33-42-12 | D02294 | | 8 | | TB0025B | A002 | 1C | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3050

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W3054 | 286N3054 | | | P62 PNL. NOSE GEAR LANDING GEAR,RIGHT (continued) | | | | | | | | | | | |
| 0017 | 12 | | HA | | 10-1 | 33-42-12 | D40488P | | R | | TB0025B | A002 | 1C | | 115-199 |
| 0018 | 12 | | HA | | 11-0 | 33-42-12 | D02294 | | 2 | | D40488P | P | | | 115-199 |
| 0019 | 18 | | HL | | 11-0 | 33-42-12 | D02294 | | 7 | | D40488P | G | | | 115-199 |
| 0020 | 20 | | HL | | 9-6 | 33-42-21 | D00190 | | 7 | | D40488P | A | | | 001-099 |
| 0020 | 20 | | HL | | 10-9 | 33-42-21 | D00190 | | 7 | | D40488P | A | | | 115-199 |
| 0021 | 16 | | HL | | 9-6 | 33-42-21 | D00190 | | 2 | | D40488P | B | | | 001-099 |
| 0021 | 16 | | HL | | 10-9 | 33-42-21 | D00190 | | 2 | | D40488P | B | | | 115-199 |
| 0022 | 16 | | HL | | 2-6 | 33-42-21 | D00190 | | 8 | | TB0225A | A005 | 1C | | 001-099 |
| 0022 | 16 | | HL | | 2-3 | 33-42-21 | D00190 | | 8 | | TB0025C | E005 | 1 | | 115-199 |
| 0023 | 16 | | HL | | 4-4 | 33-42-21 | L00080 | | = G | M | TB0225A | A005 | 1C | | 001-099 |
| 0023 | 16 | | HL | | 3-0 | 33-42-21 | L00080 | | = G | M | TB0025C | E005 | 1 | | 115-199 |
| 0024 | 16 | | HL | | 8-11 | 33-42-21 | D40488P | | L | | TB0225A | A005 | 1C | | 001-099 |
| 0024 | 16 | | HL | | 10-0 | 33-42-21 | D40488P | | L | | TB0025C | E005 | 1 | | 115-199 |
| 0025 | 16 | | HL | | 3-5 | 33-42-21 | D00190 | | 3 | | L00080 | = P | M | | 001-099 |
| 0025 | 16 | | HL | | 2-8 | 33-42-21 | D00190 | | 3 | | L00080 | = P | M | | 115-199 |
| 2001B | 18 | | HM | AB | 9-0 | 32-09-12 | D40488P | | K | | TB0025C | C005 | 1 | | 001-099 |
| 2001B | 18 | | HM | AB | 10-0 | 32-09-12 | D40488P | | K | | TB0025C | C005 | 1 | | 115-199 |
| 2001R | 18 | | HM | AB | 0-0 | 32-09-12 | D40488P | | J | | TB0025C | A005 | 1 | | ALL |
| 2501B | 20 | | HQ | AD | 9-0 | 23-41-12 | D40488P | | M | | TB0025K | C001 | 1 | | 001-099 |
| 2501R | 20 | | HQ | AD | 0-0 | 23-41-12 | D40488P | | N | | TB0025K | A001 | 1 | | 001-099 |
| 2501Z | | | | AD | 0-0 | 23-41-12 | D40488P | | X | | TB0025K | E001 | 1 | | 001-099 |
| 3501B | 20 | | HR | AA | 9-0 | 23-51-13 | D40488P | | Z | | TB0025K | C006 | 1 | | 001-099 |
| 3501B | 20 | | HR | AA | 10-0 | 23-51-13 | D40488P | | Z | | TB0025K | C006 | 1 | | 115-199 |
| 3501R | 20 | | HR | AA | 0-0 | 23-51-13 | D40488P | | Y | | TB0025K | A006 | 1 | | ALL |
| 3501Y | 20 | | HR | AA | 0-0 | 23-51-13 | D40488P | | A- | | TB0025K | E006 | 1 | | ALL |
| 3501Z | | | | AA | 0-0 | 23-51-13 | D40488P | | B- | | TB0025K | DED | | | ALL |
| 3502B | 20 | | HR | AC | 10-1 | 23-41-12 | D40488P | | M | | TB0025K | C001 | 1 | | 115-199 |
| 3502R | 20 | | HR | AC | 0-0 | 23-41-12 | D40488P | | N | | TB0025K | A001 | 1 | | 115-199 |
| 3502Y | 20 | | HR | AC | 0-0 | 23-41-12 | D40488P | | W | | TB0025K | E001 | 1 | | 115-199 |
| 3502Z | | | | AC | 0-0 | 23-41-12 | D40488P | | X | | TB0025K | DED | | | 115-199 |
| A-A | | | | | 0-0 | 23-51-13 | D00435 | | RED | | TB0025K | A006 | 1 | | ALL |
| A-B | | | | | 0-0 | 23-51-13 | D00435 | | BLU | | TB0025K | C006 | 1 | | ALL |
| A-C | | | | | 0-0 | 23-51-13 | D00435 | | BLK | | TB0025K | E006 | 1 | | ALL |
| A-D | | | | | 0-0 | 32-09-12 | S10068 | | BLU | | TB0025C | C005 | 1 | | ALL |
| A-E | | | | | 0-0 | 32-09-12 | S10068 | | RED | | TB0025C | A005 | 1 | | ALL |
| A-F | | | | | 0-0 | 23-41-12 | D00425 | | RED | | TB0025K | A001 | 1 | | ALL |
| A-G | | | | | 0-0 | 23-41-12 | D00425 | | BLU | | TB0025K | C001 | 1 | | ALL |
| A-H | | | | | 0-0 | 23-41-12 | D00425 | | BLK | | TB0025K | E001 | 1 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3050

Page 4 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|-------------------------------|------|----------|---------|-------|------|------|---------|-------|-------------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type |
| W3060 | 286N3060 | | | P62 PANEL, APU REMOTE CONTROL | | | | | | | | | | | |
| 0001 | 20 | | HL | | 3-10 | 26-15-12 | TB0225C | C001 | 1 | | L00401 | =P | \$ | | 001-099 |
| 0001 | 20 | | HL | | 2-3 | 26-15-12 | TB0025K | A007 | 1 | | L00401 | =P | \$ | | 115-199 |
| 0002 | 20 | | HL | | 1-8 | 26-15-12 | TB0025C | E007 | 1 | | L00401 | =G | C | | 001-099 |
| 0002 | 20 | | HL | | 2-3 | 26-15-12 | TB0025K | C007 | 1 | | L00401 | =G | C | | 115-199 |
| 0003 | 20 | | HL | | 2-1 | 26-15-12 | TB0225C | E004 | 1 | | B00122 | - | D | | 001-099 |
| 0003 | 20 | | HL | | 2-9 | 26-15-12 | TB0025L | A008 | 1 | | B00122 | - | D | | 115-199 |
| 0004 | 20 | | HL | | 2-4 | 26-15-12 | TB0225C | A001 | 1 | | B00122 | + | D | | 001-099 |
| 0004 | 20 | | HL | | 2-9 | 26-15-12 | TB0025K | E007 | 1 | | B00122 | + | D | | 115-199 |
| 0005 | 20 | | HL | | 3-2 | 32-44-11 | L00456 | | 3 | B | TB0025K | G001 | 1 | | 115-199 |
| 0006 | 20 | | HL | | 3-2 | 32-44-11 | L00456 | | 2 | B | TB0025K | G006 | 1 | | 115-199 |
| 0007 | 20 | | HL | | 3-2 | 32-44-11 | L00456 | | 1 | B | TB0025K | G010 | 1 | | 115-199 |
| 2501B | 20 | | HQ | AA | 2-9 | 23-71-11 | D00479 | CAP | Y | | TB0025K | A010 | 1 | | 115-199 |
| 2501R | 20 | | HQ | AA | 0-0 | 23-71-11 | D00479 | CAP | Y | | TB0025K | C010 | 1 | | 115-199 |
| 2501Z | | | | AA | 0-0 | 23-71-11 | D00479 | DED | | | TB0025K | E010 | 1 | | 115-199 |
| A-01 | | | | | 0-0 | 26-15-12 | S00484 | | 1 | | TB0025K | C008 | 1 | | 001-099 |
| A-01 | | | | | 0-0 | 26-15-12 | S00484 | | 1 | | TB0025K | A009 | 1 | | 115-199 |
| A-02 | | | | | 0-0 | 26-15-12 | S00484 | | 2 | | S00484 | CAP | Y | | ALL |
| A-03 | | | | | 0-0 | 26-15-12 | S00484 | | 3 | | TB0225C | E004 | 1 | | 001-099 |
| A-03 | | | | | 0-0 | 26-15-12 | S00484 | | 3 | | TB0025L | A008 | 1 | | 115-199 |
| A-04 | | | | | 0-0 | 26-15-12 | S00484 | | 4 | | S00484 | CAP | Y | | ALL |
| A-05 | | | | | 0-0 | 26-15-12 | S00484 | | 5 | | S00484 | CAP | Y | | ALL |
| A-06 | | | | | 0-0 | 26-15-12 | S00484 | | 6 | | S00484 | CAP | Y | | ALL |
| B-01 | | | | | 0-0 | 26-15-12 | S00485 | | 1 | | TB0025C | A007 | 1 | | 001-099 |
| B-01 | | | | | 0-0 | 26-15-12 | S00485 | | 1 | | TB0025K | E009 | 1 | | 115-199 |
| B-02 | | | | | 0-0 | 26-15-12 | S00485 | | 2 | | S00485 | CAP | Y | | ALL |
| B-03 | | | | | 0-0 | 26-22-21 | S00485 | | 3 | | TB0025C | C007 | 1 | | 001-099 |
| B-03 | | | | | 0-0 | 26-15-12 | S00485 | | 3 | | TB0025K | G009 | 1 | | 115-199 |
| B-04 | | | | | 0-0 | 26-15-12 | S00485 | | 4 | | S00485 | CAP | Y | | ALL |
| B-05 | | | | | 0-0 | 26-15-12 | S00485 | | 5 | | S00485 | CAP | Y | | ALL |
| B-06 | | | | | 0-0 | 26-15-12 | S00485 | | 6 | | S00485 | CAP | Y | | ALL |
| C-01 | | | | | 0-0 | 23-71-11 | D00479 | BLU | | | TB0025K | A011 | 1 | | 115-199 |
| C-02 | | | | | 0-0 | 23-71-11 | D00479 | RED | | | TB0025K | C011 | 1 | | 115-199 |
| C-03 | | | | | 0-0 | 23-71-11 | D00479 | BLK | | | TB0025K | E011 | 1 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3060

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3100 | | 286N3100 | | | | STA 1700 TO RUDDER STA 155 - RUD TRIM ACTUATOR & POS XMTR | | | | | | | | | |
| 0001 | 20 | GA | | | 18-2 | 27-28-11 | D40142P | | 1 | | D01742 | | 2 | | 001-099 |
| 0001 | 20 | GA | | | 18-0 | 27-28-11 | D40142P | | 1 | | D01742 | | 2 | | 115-199 |
| 0003 | 20 | GA | | | 4-7 | 27-28-11 | GD00092 | AC.. | E | | D01742 | | 1 | | 001-099 |
| 0003 | 20 | GA | | | 5-0 | 27-28-11 | GD00092 | AC.. | E | | D01742 | | 1 | | 115-199 |
| 0006 | 18 | GA | | | 3-10 | 27-21-11 | GD00090 | DC.. | E | | D01746 | | 1 | | 001-099 |
| 0006 | 18 | GA | | | 4-0 | 27-21-11 | GD00090 | DC.. | E | | D01746 | | 1 | | 115-199 |
| 0007 | 18 | GA | | | 4-0 | 27-21-11 | GD00091 | ST.. | E | | D01746 | | 12 | | ALL |
| 0008 | 20 | GA | | | 15-2 | 27-28-13 | D40142P | | 6 | | D01746 | | 6 | | 001-099 |
| 0008 | 20 | GA | | | 15-0 | 27-28-13 | D40142P | | 6 | | D01746 | | 6 | | 115-199 |
| 0009 | 20 | GA | | | 15-2 | 27-28-13 | D40142P | | 9 | | D01746 | | 7 | | 001-099 |
| 0009 | 20 | GA | | | 15-0 | 27-28-13 | D40142P | | 9 | | D01746 | | 7 | | 115-199 |
| 0010 | 20 | GA | | | 25-10 | 27-23-21 | D04714 | | 2 | | D40142P | | 11 | | 001-099 |
| 0010 | 20 | GA | | | 26-0 | 27-23-21 | D04714 | | 2 | | D40142P | | 11 | | 115-199 |
| 0011 | 20 | GA | | | 17-3 | 27-23-21 | D04710 | | 2 | | D04712 | | 1 | | 001-099 |
| 0011 | 20 | GA | | | 18-0 | 27-23-21 | D04710 | | 2 | | D04712 | | 1 | | 115-199 |
| 0012 | 18 | GA | | | 6-8 | 27-23-21 | D04710 | | 3 | | GD02007 | ST.. | E | | 001-099 |
| 0012 | 18 | GA | | | 7-0 | 27-23-21 | D04710 | | 3 | | GD02007 | ST.. | E | | 115-199 |
| 0013 | 20 | GA | | | 16-0 | 27-23-21 | D04712 | | 2 | | D04714 | | 1 | | ALL |
| 0014 | 18 | GA | | | 7-5 | 27-23-21 | D04712 | | 3 | | GD02008 | ST.. | E | | 001-099 |
| 0014 | 18 | GA | | | 8-0 | 27-23-21 | D04712 | | 3 | | GD02008 | ST.. | E | | 115-199 |
| 0015 | 20 | GA | | | 27-0 | 27-23-21 | D04710 | | 1 | | D40142P | | 10 | | ALL |
| 0016 | 18 | GA | | | 7-0 | 27-23-21 | D04714 | | 3 | | GD02009 | ST.. | E | | ALL |
| 1001 | 20 | GE | A | | 18-2 | 27-28-11 | D40142P | | 16 | | D01742 | | 3 | | 001-099 |
| 1001 | 20 | GE | A | | 18-0 | 27-28-11 | D40142P | | 16 | | D01742 | | 3 | | 115-199 |
| 1001Z | | | A | | 0-0 | 27-28-11 | D40142P | | 17 | | D01742 | DED | | | ALL |
| 2001B | 20 | GB | AA | | 18-2 | 27-28-11 | D40142P | | 2 | | D01742 | | 4 | | 001-099 |
| 2001B | 20 | GB | AA | | 18-0 | 27-28-11 | D40142P | | 2 | | D01742 | | 4 | | 115-199 |
| 2001R | 20 | GB | AA | | 0-0 | 27-28-11 | D40142P | | 3 | | D01742 | | 5 | | ALL |
| 2002B | 20 | GB | AB | | 15-2 | 27-28-13 | D40142P | | 7 | | D01746 | | 5 | | 001-099 |
| 2002B | 20 | GB | AB | | 15-0 | 27-28-13 | D40142P | | 7 | | D01746 | | 5 | | 115-199 |
| 2002R | 20 | GB | AB | | 0-0 | 27-28-13 | D40142P | | 8 | | D01746 | | 4 | | ALL |
| 2501B | 18 | GF | AC | | 15-2 | 27-21-11 | D40142P | | 4 | 18 | D01746 | | 2 | | 001-099 |
| 2501B | 18 | GF | AC | | 15-0 | 27-21-11 | D40142P | | 4 | 18 | D01746 | | 2 | | 115-199 |
| 2501R | 18 | GF | AC | | 0-0 | 27-21-11 | D40142P | | 15 | 18 | D01746 | | 3 | | ALL |
| 2501Z | | | AC | | 0-0 | 27-21-11 | D40142P | | DED | | D01746 | DED | | | ALL |
| W3101 | | 286N3101 | | | | AFT BODY DISC TO LEFT A/P ROLLOUT GUIDANCE SERVO-CHANNEL L | | | | | | | | | |
| 0001 | 20 | GA | | | 13-0 | 22-11-12 | D40471P | | 3 | | D00031 | | 2 | | 001-099 |
| 0001 | 20 | GA | | | 12-6 | 22-11-12 | D40471P | | 3 | | D00031 | | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3100

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3101 | 286N3101 | | | AFT BODY DISC TO LEFT A/P ROLLOUT GUIDANCE SERVO-CHANNEL L (continued) | | | | | | | | | | | |
| 0002 | 20 | | GA | | 13-0 | 22-11-12 | D40471P | | 24 | | D00031 | | 18 | | 001-099 |
| 0002 | 20 | | GA | | 12-6 | 22-11-12 | D40471P | | 24 | | D00031 | | 18 | | 115-199 |
| 0003 | 20 | | GA | | 4-0 | 22-11-12 | D00031 | | 17 | | GD00025 | DC.. | E | | 001-099 |
| 0003 | 20 | | GA | | 3-7 | 22-11-12 | D00031 | | 17 | | GD00025 | DC.. | E | | 115-199 |
| 0004 | 20 | | GA | | 4-0 | 22-11-12 | D00031 | | 1 | | GD00025 | DC.. | E | | 001-099 |
| 0004 | 20 | | GA | | 3-7 | 22-11-12 | D00031 | | 1 | | GD00025 | DC.. | E | | 115-199 |
| 0005 | 20 | | GA | | 4-0 | 22-11-12 | D00031 | | 19 | | GD00026 | ST.. | E | | 001-099 |
| 0005 | 20 | | GA | | 3-7 | 22-11-12 | D00031 | | 19 | | GD00026 | ST.. | E | | 115-199 |
| 2001B | 20 | | GB | AA | 13-0 | 22-11-11 | D40471P | | 2 | | SM00002 | | 9 | | 001-099 |
| 2001B | 20 | | GB | AA | 12-0 | 22-11-11 | D40471P | | 2 | | SM00002 | | 9 | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 22-11-11 | D40471P | | 1 | | SM00001 | | 9 | | ALL |
| 2002B | 20 | | GB | AB | 4-0 | 22-11-11 | SM00002 | | 9 | | D00031 | | 12 | | 001-099 |
| 2002B | 20 | | GB | AB | 1-1 | 22-11-11 | SM00002 | | 9 | | D00031 | | 12 | | 115-199 |
| 2002R | 20 | | GB | AB | 0-0 | 22-11-11 | SM00001 | | 9 | | D00031 | | 13 | | ALL |
| 2003B | 20 | | GB | AC | 4-0 | 22-11-11 | SM00002 | | 9 | | D00031 | | 7 | | 001-099 |
| 2003B | 20 | | GB | AC | 1-1 | 22-11-11 | SM00002 | | 9 | | D00031 | | 7 | | 115-199 |
| 2003R | 20 | | GB | AC | 0-0 | 22-11-11 | SM00001 | | 9 | | D00031 | | 8 | | ALL |
| 2004B | 20 | | GB | AD | 13-0 | 22-13-11 | D40471P | | 6 | | D00031 | | 6 | | 001-099 |
| 2004B | 20 | | GB | AD | 12-6 | 22-13-11 | D40471P | | 6 | | D00031 | | 6 | | 115-199 |
| 2004R | 20 | | GB | AD | 0-0 | 22-13-11 | D40471P | | 16 | | D00031 | | 5 | | ALL |
| 3001B | 20 | | GC | AG | 13-0 | 22-13-11 | D40471P | | 8 | | D00031 | | 10 | | 001-099 |
| 3001B | 20 | | GC | AG | 12-6 | 22-13-11 | D40471P | | 8 | | D00031 | | 10 | | 115-199 |
| 3001R | 20 | | GC | AG | 0-0 | 22-13-11 | D40471P | | 7 | | D00031 | | 11 | | ALL |
| 3001Y | 20 | | GC | AG | 0-0 | 22-13-11 | D40471P | | 9 | | D00031 | | 9 | | ALL |
| 3002B | 20 | | GC | AH | 13-0 | 22-13-11 | D40471P | | 12 | | D00031 | | 15 | | 001-099 |
| 3002B | 20 | | GC | AH | 12-6 | 22-13-11 | D40471P | | 12 | | D00031 | | 15 | | 115-199 |
| 3002R | 20 | | GC | AH | 0-0 | 22-13-11 | D40471P | | 11 | | D00031 | | 16 | | ALL |
| 3002Y | 20 | | GC | AH | 0-0 | 22-13-11 | D40471P | | 13 | | D00031 | | 14 | | ALL |
| 3003B | 20 | | GC | AJ | 13-0 | 22-13-11 | D40471P | | 18 | | D00031 | CAP | Y | | 001-099 |
| 3003B | 20 | | GC | AJ | 12-6 | 22-13-11 | D40471P | | 18 | | D00031 | CAP | Y | | 115-199 |
| 3003R | 20 | | GC | AJ | 0-0 | 22-13-11 | D40471P | | 17 | | D00031 | CAP | Y | | ALL |
| 3003Y | 20 | | GC | AJ | 0-0 | 22-13-11 | D40471P | | 19 | | D00031 | CAP | Y | | ALL |
| W3103 | 286N3103 | | | AFT BODY DISC. TO RUDDER RATIO CHANGER AND YAW DAMPER SERVO -CH LB | | | | | | | | | | | |
| 0001 | 20 | | GA | | 14-0 | 27-21-12 | D40475P | | 8 | | D00381 | | 2 | | 001-099 |
| 0001 | 20 | | GA | | 15-0 | 27-21-12 | D40475P | | 8 | | D00381 | | 2 | | 115-199 |
| 0002 | 18 | | GA | | 16-0 | 22-21-11 | D40475P | | 21 | | D00345 | | 2 | | 001-099 |
| 0002 | 18 | | GA | | 17-0 | 22-21-11 | D40475P | | 21 | | D00345 | | 2 | | 115-199 |
| 0003 | 18 | | GA | | 4-0 | 22-21-11 | D00345 | | 1 | | GD00142 | DC.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3100

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|------------------------|------------------------|------------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W3103 | 286N3103 | AFT BODY DISC. TO RUDDER RATIO CHANGER AND YAW DAMPER SERVO -CH LB (continued) | | | |
| 0004 | 18 GA | 4-0 22-21-11 | D00345 10 | GD00143 ST.. E | ALL |
| 0005 | 20 GA | 5-0 27-21-12 | D00715 1 | GD00144 ST.. E | ALL |
| 0006 | 20 GA | 4-0 27-21-12 | D00381 3 | GD00004 DC.. E | ALL |
| 0007 | 20 GA | 4-0 27-21-12 | D00381 7 | GD00198 ST.. E | ALL |
| 2001B | 20 GB AA | 15-0 27-21-12 | D40475P 2 | D00715 7 | 001-099 |
| 2001B | 20 GB AA | 16-0 27-21-12 | D40475P 2 | D00715 7 | 115-199 |
| 2001R | 20 GB AA | 0-0 27-21-12 | D40475P 1 | D00715 6 | ALL |
| 2002B | 20 GB AC | 14-0 27-21-12 | D40475P 7 | D00381 6 | 001-099 |
| 2002B | 20 GB AC | 15-0 27-21-12 | D40475P 7 | D00381 6 | 115-199 |
| 2002R | 20 GB AC | 0-0 27-21-12 | D40475P 6 | D00381 5 | ALL |
| 2003B | 20 GB AD | 16-0 22-21-11 | D40475P 11 | D00345 3 | 001-099 |
| 2003B | 20 GB AD | 17-0 22-21-11 | D40475P 11 | D00345 3 | 115-199 |
| 2003R | 20 GB AD | 0-0 22-21-11 | D40475P 10 | D00345 4 | ALL |
| 2004B | 20 GB AF | 16-0 22-21-11 | D40475P 16 | D00345 6 | 001-099 |
| 2004B | 20 GB AF | 17-0 22-21-11 | D40475P 16 | D00345 6 | 115-199 |
| 2004R | 20 GB AF | 0-0 22-21-11 | D40475P 15 | D00345 5 | ALL |
| 2005B | 20 GB AG | 15-0 27-21-12 | D40475P 18 | D00715 CAP Y | 001-099 |
| 2005B | 20 GB AG | 16-0 27-21-12 | D40475P 18 | D00715 CAP Y | 115-199 |
| 2005R | 20 GB AG | 0-0 27-21-12 | D40475P 17 | D00715 CAP Y | ALL |
| 2006B | 20 GB AH | 14-0 27-21-12 | D40475P 20 | D00381 CAP Y | 001-099 |
| 2006B | 20 GB AH | 15-0 27-21-12 | D40475P 20 | D00381 CAP Y | 115-199 |
| 2006R | 20 GB AH | 0-0 27-21-12 | D40475P 19 | D00381 CAP Y | ALL |
| 2007B | 20 GB AJ | 16-0 22-21-11 | D40475P 25 | D00345 CAP Y | 001-099 |
| 2007B | 20 GB AJ | 17-0 22-21-11 | D40475P 25 | D00345 CAP Y | 115-199 |
| 2007R | 20 GB AJ | 0-0 22-21-11 | D40475P 24 | D00345 CAP Y | ALL |
| 3001B | 20 GC AB | 15-0 27-21-12 | D40475P 4 | D00715 3 | 001-099 |
| 3001B | 20 GC AB | 16-0 27-21-12 | D40475P 4 | D00715 3 | 115-199 |
| 3001R | 20 GC AB | 0-0 27-21-12 | D40475P 3 | D00715 2 | ALL |
| 3001Y | 20 GC AB | 0-0 27-21-12 | D40475P 5 | D00715 4 | ALL |
| 3002B | 20 GC AE | 16-0 22-21-11 | D40475P 13 | D00345 9 | 001-099 |
| 3002B | 20 GC AE | 17-0 22-21-11 | D40475P 13 | D00345 9 | 115-199 |
| 3002R | 20 GC AE | 0-0 22-21-11 | D40475P 12 | D00345 8 | ALL |
| 3002Y | 20 GC AE | 0-0 22-21-11 | D40475P 14 | D00345 7 | ALL |
| W3107 | 286N3107 | HF-L RF COAX, AA1671 TO ANT COUPLER | | | |
| 001CO | AA | 0-0 23-11-11 | D00315 =C1 | D40193J =C1 | ALL |
| 001CX | BS AA | 25-2 23-11-11 | D00315 =A1 | D40193J =A1 | 001-008, 115-199 |
| 001CX | 65 AA | 25-2 23-11-11 | D00315 =A1 | D40193J =A1 | 009-099 |

WIRE LIST

D280N032

91-21-11

Section W3100

Page 3 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3111 | 286N3111 | | | AFT BODY DISCONNECT TO RIGHT A/P ROLLOUT GUIDANCE SERVO -CH R | | | | | | | | | | | |
| 0001 | 20 | | GA | | 12-0 | 22-11-22 | D40487P | | 3 | | D00071 | | 2 | | 001-099 |
| 0001 | 20 | | GA | | 13-0 | 22-11-22 | D40487P | | 3 | | D00071 | | 2 | | 115-199 |
| 0002 | 20 | | GA | | 12-0 | 22-11-22 | D40487P | | 24 | | D00071 | | 18 | | 001-099 |
| 0002 | 20 | | GA | | 13-0 | 22-11-22 | D40487P | | 24 | | D00071 | | 18 | | 115-199 |
| 0003 | 20 | | GA | | 3-7 | 22-11-22 | D00071 | | 17 | | GD00005 | DC.R | E | | 001-099 |
| 0003 | 20 | | GA | | 4-0 | 22-11-22 | D00071 | | 17 | | GD00005 | DC.R | E | | 115-199 |
| 0004 | 20 | | GA | | 3-7 | 22-11-22 | D00071 | | 1 | | GD00005 | DC.R | E | | 001-099 |
| 0004 | 20 | | GA | | 4-0 | 22-11-22 | D00071 | | 1 | | GD00005 | DC.R | E | | 115-199 |
| 0005 | 20 | | GA | | 3-9 | 22-11-22 | D00071 | | 19 | | GD00006 | ST.R | E | | 001-099 |
| 0005 | 20 | | GA | | 4-0 | 22-11-22 | D00071 | | 19 | | GD00006 | ST.R | E | | 115-199 |
| 2001B | 20 | | GB | AA | 11-6 | 22-11-21 | D40487P | | 2 | | SM00002 | | 9 | | 001-099 |
| 2001B | 20 | | GB | AA | 13-0 | 22-11-21 | D40487P | | 2 | | SM00002 | | 9 | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 22-11-21 | D40487P | | 1 | | SM00001 | | 9 | | ALL |
| 2002B | 20 | | GB | AB | 1-0 | 22-11-21 | SM00002 | | 9 | | D00071 | | 12 | | ALL |
| 2002R | 20 | | GB | AB | 0-0 | 22-11-21 | SM00001 | | 9 | | D00071 | | 13 | | ALL |
| 2003B | 20 | | GB | AC | 1-0 | 22-11-21 | SM00002 | | 9 | | D00071 | | 7 | | ALL |
| 2003R | 20 | | GB | AC | 0-0 | 22-11-21 | SM00001 | | 9 | | D00071 | | 8 | | ALL |
| 2004B | 20 | | GB | AD | 12-0 | 22-13-21 | D40487P | | 6 | | D00071 | | 6 | | 001-099 |
| 2004B | 20 | | GB | AD | 13-0 | 22-13-21 | D40487P | | 6 | | D00071 | | 6 | | 115-199 |
| 2004R | 20 | | GB | AD | 0-0 | 22-13-21 | D40487P | | 16 | | D00071 | | 5 | | ALL |
| 3001B | 20 | | GC | AG | 12-0 | 22-13-21 | D40487P | | 8 | | D00071 | | 10 | | 001-099 |
| 3001B | 20 | | GC | AG | 13-0 | 22-13-21 | D40487P | | 8 | | D00071 | | 10 | | 115-199 |
| 3001R | 20 | | GC | AG | 0-0 | 22-13-21 | D40487P | | 7 | | D00071 | | 11 | | ALL |
| 3001Y | 20 | | GC | AG | 0-0 | 22-13-21 | D40487P | | 9 | | D00071 | | 9 | | ALL |
| 3002B | 20 | | GC | AH | 12-0 | 22-13-21 | D40487P | | 12 | | D00071 | | 15 | | 001-099 |
| 3002B | 20 | | GC | AH | 13-0 | 22-13-21 | D40487P | | 12 | | D00071 | | 15 | | 115-199 |
| 3002R | 20 | | GC | AH | 0-0 | 22-13-21 | D40487P | | 11 | | D00071 | | 16 | | ALL |
| 3002Y | 20 | | GC | AH | 0-0 | 22-13-21 | D40487P | | 13 | | D00071 | | 14 | | ALL |
| 3003B | 20 | | GC | AJ | 12-0 | 22-13-21 | D40487P | | 18 | | D00071 | CAP | Y | | 001-099 |
| 3003B | 20 | | GC | AJ | 13-0 | 22-13-21 | D40487P | | 18 | | D00071 | CAP | Y | | 115-199 |
| 3003R | 20 | | GC | AJ | 0-0 | 22-13-21 | D40487P | | 17 | | D00071 | CAP | Y | | ALL |
| 3003Y | 20 | | GC | AJ | 0-0 | 22-13-21 | D40487P | | 19 | | D00071 | CAP | Y | | ALL |
| W3113 | 286N3113 | | | AFT BODY DISC TO RUDDER RATIO CHANGER AND YAW DAMPER SERVO,R CH RA | | | | | | | | | | | |
| 0001 | 18 | | GA | | 17-0 | 22-21-21 | D40489P | | 21 | | D00347 | | 2 | | ALL |
| 0002 | 18 | | GA | | 4-0 | 22-21-21 | D00347 | | 1 | | GD00145 | DC.. | E | | ALL |
| 0003 | 18 | | GA | | 4-0 | 22-21-21 | D00347 | | 10 | | GD00146 | ST.. | E | | ALL |
| 0004 | 20 | | GA | | 4-0 | 27-21-22 | D00717 | | 1 | | GD00144 | ST.. | E | | ALL |
| 2001B | 20 | | GB | AA | 15-0 | 27-21-22 | D40489P | | 2 | | D00717 | | 7 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3110

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W3113 | 286N3113 | | | AFT BODY DISC TO RUDDER RATIO CHANGER AND YAW DAMPER SERVO,R CH RA (continued) | | | | | | | | | | | |
| 2001R | 20 | GB | AA | 0-0 | 27-21-22 | D40489P | | 1 | | | D00717 | | 6 | | ALL |
| 2002B | 20 | GB | AC | 14-0 | 27-21-22 | D40489P | | 7 | | | D00461 | | 2 | | ALL |
| 2002R | 20 | GB | AC | 0-0 | 27-21-22 | D40489P | | 6 | | | D00461 | | 1 | | ALL |
| 2003B | 20 | GB | AD | 17-0 | 22-21-21 | D40489P | | 9 | | | D00347 | | 3 | | ALL |
| 2003R | 20 | GB | AD | 0-0 | 22-21-21 | D40489P | | 8 | | | D00347 | | 4 | | ALL |
| 2004B | 20 | GB | AF | 17-0 | 22-21-21 | D40489P | | 14 | | | D00347 | | 6 | | ALL |
| 2004R | 20 | GB | AF | 0-0 | 22-21-21 | D40489P | | 13 | | | D00347 | | 5 | | ALL |
| 2005B | 20 | GB | AG | 15-0 | 27-21-22 | D40489P | | 18 | | | D00717 | CAP | Y | | ALL |
| 2005R | 20 | GB | AG | 0-0 | 27-21-22 | D40489P | | 17 | | | D00717 | CAP | Y | | ALL |
| 2006B | 20 | GB | AH | 14-0 | 27-21-22 | D40489P | | 20 | | | D00461 | CAP | Y | | ALL |
| 2006R | 20 | GB | AH | 0-0 | 27-21-22 | D40489P | | 19 | | | D00461 | CAP | Y | | ALL |
| 2007B | 20 | GB | AJ | 17-0 | 22-21-21 | D40489P | | 25 | | | D00347 | CAP | Y | | ALL |
| 2007R | 20 | GB | AJ | 0-0 | 22-21-21 | D40489P | | 24 | | | D00347 | CAP | Y | | ALL |
| 3001B | 20 | GC | AB | 15-0 | 27-21-22 | D40489P | | 4 | | | D00717 | | 3 | | ALL |
| 3001R | 20 | GC | AB | 0-0 | 27-21-22 | D40489P | | 3 | | | D00717 | | 2 | | ALL |
| 3001Y | 20 | GC | AB | 0-0 | 27-21-22 | D40489P | | 5 | | | D00717 | | 4 | | ALL |
| 3002B | 20 | GC | AE | 17-0 | 22-21-21 | D40489P | | 11 | | | D00347 | | 9 | | ALL |
| 3002R | 20 | GC | AE | 0-0 | 22-21-21 | D40489P | | 10 | | | D00347 | | 8 | | ALL |
| 3002Y | 20 | GC | AE | 0-0 | 22-21-21 | D40489P | | 12 | | | D00347 | | 7 | | ALL |
| W3117 | 286N3117 | | | HF-R RF COAX, AB1671 TO ANT COUPLER | | | | | | | | | | | |
| 001CO | | | AA | 0-0 | 23-11-21 | D00317 | | =C1 | | | D40197J | | =C1 | | ALL |
| 001CX | | BS | AA | 25-0 | 23-11-21 | D00317 | | =A1 | | | D40197J | | =A1 | | 001-008, 115-199 |
| 001CX | | 65 | AA | 24-1 | 23-11-21 | D00317 | | =A1 | | | D40197J | | =A1 | | 009-099 |

WIRE LIST

D280N032

91-21-11

Section W3110

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3121 | 286N3121 | | | AFT BODY DISC TO A/P ROLLOUT GUIDANCE SERVO -CHANNEL C | | | | | | | | | | | |
| 0001 | 20 | | GA | | 12-0 | 22-11-32 | D40473P | | 3 | | D00051 | | 2 | | 001-099 |
| 0001 | 20 | | GA | | 13-0 | 22-11-32 | D40473P | | 3 | | D00051 | | 2 | | 115-199 |
| 0002 | 20 | | GA | | 12-0 | 22-11-32 | D40473P | | 24 | | D00051 | | 18 | | 001-099 |
| 0002 | 20 | | GA | | 13-0 | 22-11-32 | D40473P | | 24 | | D00051 | | 18 | | 115-199 |
| 0003 | 20 | | GA | | 4-0 | 22-11-32 | D00051 | | 17 | | GD00007 | DC.C | E | | ALL |
| 0004 | 20 | | GA | | 4-0 | 22-11-32 | D00051 | | 1 | | GD00007 | DC.C | E | | ALL |
| 0005 | 20 | | GA | | 4-0 | 22-11-32 | D00051 | | 19 | | GD00008 | ST.C | E | | ALL |
| 2001B | 20 | | GB | AA | 12-0 | 22-11-31 | D40473P | | 2 | | SM00002 | | 9 | | 001-099 |
| 2001B | 20 | | GB | AA | 13-0 | 22-11-31 | D40473P | | 2 | | SM00002 | | 9 | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 22-11-31 | D40473P | | 1 | | SM00001 | | 9 | | ALL |
| 2002B | 20 | | GB | AB | 2-0 | 22-11-31 | SM00002 | | 9 | | D00051 | | 12 | | ALL |
| 2002R | 20 | | GB | AB | 0-0 | 22-11-31 | SM00001 | | 9 | | D00051 | | 13 | | ALL |
| 2003B | 20 | | GB | AC | 2-0 | 22-11-31 | SM00002 | | 9 | | D00051 | | 7 | | ALL |
| 2003R | 20 | | GB | AC | 0-0 | 22-11-31 | SM00001 | | 9 | | D00051 | | 8 | | ALL |
| 2004B | 20 | | GB | AD | 12-0 | 22-13-31 | D40473P | | 6 | | D00051 | | 6 | | 001-099 |
| 2004B | 20 | | GB | AD | 13-0 | 22-13-31 | D40473P | | 6 | | D00051 | | 6 | | 115-199 |
| 2004R | 20 | | GB | AD | 0-0 | 22-13-31 | D40473P | | 16 | | D00051 | | 5 | | ALL |
| 3001B | 20 | | GC | AG | 12-0 | 22-13-31 | D40473P | | 8 | | D00051 | | 10 | | 001-099 |
| 3001B | 20 | | GC | AG | 13-0 | 22-13-31 | D40473P | | 8 | | D00051 | | 10 | | 115-199 |
| 3001R | 20 | | GC | AG | 0-0 | 22-13-31 | D40473P | | 7 | | D00051 | | 11 | | ALL |
| 3001Y | 20 | | GC | AG | 0-0 | 22-13-31 | D40473P | | 9 | | D00051 | | 9 | | ALL |
| 3002B | 20 | | GC | AH | 12-0 | 22-13-31 | D40473P | | 12 | | D00051 | | 15 | | 001-099 |
| 3002B | 20 | | GC | AH | 13-0 | 22-13-31 | D40473P | | 12 | | D00051 | | 15 | | 115-199 |
| 3002R | 20 | | GC | AH | 0-0 | 22-13-31 | D40473P | | 11 | | D00051 | | 16 | | ALL |
| 3002Y | 20 | | GC | AH | 0-0 | 22-13-31 | D40473P | | 13 | | D00051 | | 14 | | ALL |
| 3003B | 20 | | GC | AI | 12-0 | 22-13-31 | D40473P | | 14 | | D00051 | CAP | Y | | 001-099 |
| 3003B | 20 | | GC | AI | 13-0 | 22-13-31 | D40473P | | 14 | | D00051 | CAP | Y | | 115-199 |
| 3003R | 20 | | GC | AI | 0-0 | 22-13-31 | D40473P | | 10 | | D00051 | CAP | Y | | ALL |
| 3003Y | 20 | | GC | AI | 0-0 | 22-13-31 | D40473P | | 15 | | D00051 | CAP | Y | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3120

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3133 | | 286N3133 | | | | HF-L COMM, STA 1685 TO ANT COUPLER | | | | | | | | | |
| 0001 | 20 | GA | | | 24-0 | 23-11-11 | D00307 | | F | | D41733J | 1 | | | ALL |
| 0002 | 20 | GA | | | 24-0 | 23-11-11 | D00307 | | H | | D41733J | 2 | | | ALL |
| 0003 | 20 | GA | | | 24-0 | 23-11-11 | D00307 | | L | | D41733J | 3 | | | ALL |
| 0004 | 20 | GA | | | 24-0 | 23-11-11 | D00307 | | S | | D41733J | 4 | | | ALL |
| 0005 | 20 | GA | | | 24-0 | 23-11-11 | D00307 | | K | | D41733J | 5 | | | ALL |
| 0006 | 20 | GA | | | 24-0 | 23-11-11 | D00307 | | A | | D41733J | 6 | | | ALL |
| 0007 | 20 | GA | | | 24-0 | 23-11-11 | D00307 | | R | | D41733J | 7 | | | ALL |
| 0008 | 20 | GA | | | 24-0 | 23-11-11 | D00307 | | J | | D41733J | 8 | | | ALL |
| 0009 | 20 | GA | | | 34-0 | 23-11-11 | D00307 | | X | | SP00001 | | 9 | | ALL |
| 0010 | 20 | GA | | | 34-0 | 23-11-11 | D00307 | | Y | | SP00003 | | 9 | | ALL |
| 0011 | 20 | GA | | | 3-7 | 23-11-11 | D00307 | | D | | GD00076 | AC.. | E | | ALL |
| 0012 | 20 | GA | | | 3-7 | 23-11-11 | D00307 | | G | | GD00077 | ST.. | E | | ALL |
| 0013 | 20 | GA | | | 24-0 | SPARE | D00307 | CAP | Y | | D41733J | 9 | | | 001-099 |
| 0014 | 20 | GA | | | 24-0 | SPARE | D00307 | CAP | Y | | D41733J | 10 | | | 001-099 |
| 0015 | 20 | GA | | | 24-0 | SPARE | D00307 | CAP | Y | | D41733J | 11 | | | 001-099 |
| W3135 | | 286N3135 | | | | HF-R COMM, STA 1685 TO ANT COUPLER | | | | | | | | | |
| 0001 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | F | | D41735P | 1 | | | 001-099 |
| 0001 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | F | | D41735J | 1 | | | 115-199 |
| 0002 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | H | | D41735P | 2 | | | 001-099 |
| 0002 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | H | | D41735J | 2 | | | 115-199 |
| 0003 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | L | | D41735P | 3 | | | 001-099 |
| 0003 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | L | | D41735J | 3 | | | 115-199 |
| 0004 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | S | | D41735P | 4 | | | 001-099 |
| 0004 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | S | | D41735J | 4 | | | 115-199 |
| 0005 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | K | | D41735P | 5 | | | 001-099 |
| 0005 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | K | | D41735J | 5 | | | 115-199 |
| 0006 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | A | | D41735P | 6 | | | 001-099 |
| 0006 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | A | | D41735J | 6 | | | 115-199 |
| 0007 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | R | | D41735P | 7 | | | 001-099 |
| 0007 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | R | | D41735J | 7 | | | 115-199 |
| 0008 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | J | | D41735P | 8 | | | 001-099 |
| 0008 | 20 | GA | | | 23-0 | 23-11-21 | D00309 | | J | | D41735J | 8 | | | 115-199 |
| 0009 | 20 | GA | | | 32-0 | 23-11-21 | D00309 | | X | | SP00003 | | 9 | | 001-099 |
| 0009 | 20 | GA | | | 32-0 | 23-11-11 | D00309 | | X | | SP00003 | | 9 | | 115-199 |
| 0010 | 20 | GA | | | 32-0 | 23-11-21 | D00309 | | Y | | SP00001 | | 9 | | 001-099 |
| 0010 | 20 | GA | | | 32-0 | 23-11-11 | D00309 | | Y | | SP00001 | | 9 | | 115-199 |
| 0011 | 20 | GA | | | 3-7 | 23-11-21 | D00309 | | D | | GD00078 | AC.. | E | | ALL |
| 0012 | 20 | GA | | | 3-7 | 23-11-21 | D00309 | | G | | GD00079 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3130

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|---------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3135 | 286N3135 | | | HF-R COMM, STA 1685 TO ANT COUPLER (continued) | | | | | | | | | | | |
| 0013 | 20 | | GA | | 23-0 | SPARE | D00309 | CAP | Y | | D41735P | | 9 | | 001-099 |
| 0013 | 20 | | GA | | 23-0 | SPARE | D00309 | CAP | Y | | D41735J | | 9 | | 115-199 |
| 0014 | 20 | | GA | | 23-0 | SPARE | D00309 | CAP | Y | | D41735P | | 10 | | 001-099 |
| 0014 | 20 | | GA | | 23-0 | SPARE | D00309 | CAP | Y | | D41735J | | 10 | | 115-199 |
| 0015 | 20 | | GA | | 23-0 | SPARE | D00309 | CAP | Y | | D41735P | | 11 | | 001-099 |
| 0015 | 20 | | GA | | 23-0 | SPARE | D00309 | CAP | Y | | D41735J | | 11 | | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W3130
Page 2 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3200 286N3200 LEFT ELEVATOR POS. XMTR | | | | | | | | | | | | | | | |
| 0003 | 20 | | HL | | 16-0 | 27-23-21 | D04716 | | 1 | | D41112P | 6 | | | ALL |
| 0004 | 20 | | HL | | 8-0 | 27-23-21 | D04716 | | 2 | | D04718 | 1 | | | ALL |
| 0005 | 18 | | HL | | 2-0 | 27-23-21 | D04716 | | 3 | | GD02010 | ST.. | E | | ALL |
| 0006 | 20 | | HL | | 6-0 | 27-23-21 | D04718 | | 2 | | D04720 | 1 | | | ALL |
| 0007 | 18 | | HL | | 2-0 | 27-23-21 | D04718 | | 3 | | GD02011 | ST.. | E | | ALL |
| 0008 | 20 | | HL | | 13-0 | 27-23-21 | D04720 | | 2 | | D41112P | 7 | | | ALL |
| 0009 | 18 | | HL | | 2-0 | 27-23-21 | D04720 | | 3 | | GD02012 | ST.. | E | | ALL |
| 1001 | 20 | | GE | A | 6-0 | 27-38-11 | D02068 | | 3 | | D41112P | 8 | | | ALL |
| 1001Z | | | | A | 0-0 | 27-38-11 | GD02617 | ST.. | E | | GD02619 | ST.. | E | | ALL |
| 2501B | 20 | | GF | AB | 6-0 | 27-38-11 | D02068 | | 1 | | D41112P | 1 | | | ALL |
| 2501R | 20 | | GF | AB | 0-0 | 27-38-11 | D02068 | | 2 | | D41112P | 2 | | | ALL |
| 2501Z | | | | AB | 0-0 | 27-38-11 | GD02617 | ST.. | E | * | GD02619 | ST.. | E | * | ALL |
| 2502B | 20 | | GF | AC | 6-0 | 27-38-11 | D02068 | | 4 | | D41112P | 4 | | | ALL |
| 2502R | 20 | | GF | AC | 0-0 | 27-38-11 | D02068 | | 5 | | D41112P | 5 | | | ALL |
| 2502Z | | | | AC | 0-0 | 27-38-11 | GD02617 | ST.. | E | * | GD02619 | ST.. | E | * | ALL |
| W3202 286N3202 RIGHT ELEVATOR POS. XMTR | | | | | | | | | | | | | | | |
| 0003 | 20 | | HL | | 16-0 | 27-23-21 | D04690 | | 1 | | D41114P | 6 | | | ALL |
| 0004 | 20 | | HL | | 7-0 | 27-23-21 | D04690 | | 2 | | D04692 | 1 | | | ALL |
| 0005 | 18 | | HL | | 1-0 | 27-23-21 | D04690 | | 3 | | GD02004 | ST.. | E | | ALL |
| 0006 | 20 | | HL | | 7-0 | 27-23-21 | D04692 | | 2 | | D04694 | 1 | | | ALL |
| 0007 | 18 | | HL | | 2-0 | 27-23-21 | D04692 | | 3 | | GD02005 | ST.. | E | | ALL |
| 0008 | 20 | | HL | | 15-0 | 27-23-21 | D04694 | | 2 | | D41114P | 7 | | | ALL |
| 0009 | 18 | | HL | | 1-0 | 27-23-21 | D04694 | | 3 | | GD02006 | ST.. | E | | ALL |
| 1001 | 20 | | GE | A | 6-0 | 27-38-11 | D02106 | | 3 | | D41114P | 8 | | | ALL |
| 1001Z | | | | A | 0-0 | 27-38-11 | GD02611 | ST.. | E | | GD02613 | ST.. | E | | ALL |
| 2501B | 20 | | GF | AB | 6-0 | 27-38-11 | D02106 | | 1 | | D41114P | 1 | | | ALL |
| 2501R | 20 | | GF | AB | 0-0 | 27-38-11 | D02106 | | 2 | | D41114P | 2 | | | ALL |
| 2501Z | | | | AB | 0-0 | 27-38-11 | GD02611 | ST.. | E | * | GD02613 | ST.. | E | * | ALL |
| 2502B | 20 | | GF | AC | 6-0 | 27-38-11 | D02106 | | 4 | | D41114P | 4 | | | ALL |
| 2502R | 20 | | GF | AC | 0-0 | 27-38-11 | D02106 | | 5 | | D41114P | 5 | | | ALL |
| 2502Z | | | | AC | 0-0 | 27-38-11 | GD02611 | ST.. | E | * | GD02613 | ST.. | E | * | ALL |
| W3204 286N3204 LOGO LIGHTS - LEFT | | | | | | | | | | | | | | | |
| 0001 | 12 | | HA | | 3-4 | 33-45-11 | D04758 | | 1 | | GD02342 | AC.. | E | | ALL |
| 0002 | 12 | | HA | | 2-5 | 33-45-11 | D04756 | | 1 | | GD02342 | AC.. | E | | ALL |
| 0003 | 12 | | HA | | 4-0 | 33-45-11 | D04756 | | 5 | | D04758 | 5 | | | ALL |
| 0004 | 18 | | HL | | 24-6 | 33-45-11 | D04756 | | 8 | | D42044P | 1 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3200

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|----------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3206 | 286N3206 | | | LOGO LIGHTS - RIGHT | | | | | | | | | | | |
| 0001 | 12 | | HA | | 3-4 | 33-45-11 | D04816 | | 1 | | GD02344 | AC.. | E | | ALL |
| 0002 | 12 | | HA | | 2-5 | 33-45-11 | D04814 | | 1 | | GD02344 | AC.. | E | | ALL |
| 0003 | 12 | | HA | | 4-0 | 33-45-11 | D04814 | | 5 | | D04816 | | 5 | | ALL |
| 0004 | 18 | | HL | | 24-3 | 33-45-11 | D04814 | | 8 | | D42098P | | 1 | | ALL |

WIRE LIST
D280N032

91-21-11
Section W3200
Page 2 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3300 | | 286N3300 | | | | LEFT ENGINE STRUT TO LEFT FRONT/SPAR DISC | | | | | | | | | |
| 0002 | 18 | GA | | | 22-0 | 26-13-11 | D42282P | 2 | | | D40014P | 2 | | | 001-099 |
| 0002 | 18 | GA | | | 21-0 | 26-13-11 | D42282P | 2 | | | D40014P | 2 | | | 115-199 |
| 0003 | 18 | GA | | | 22-0 | 26-13-11 | D42282P | 5 | | | D40014P | 5 | | | 001-099 |
| 0003 | 18 | GA | | | 21-0 | 26-13-11 | D42282P | 5 | | | D40014P | 5 | | | 115-199 |
| 0005 | 20 | GA | | | 22-0 | 29-11-11 | D42282P | 1 | | | D40014P | 1 | | | 001-099 |
| 0005 | 20 | GA | | | 21-0 | 29-11-11 | D42282P | 1 | | | D40014P | 1 | | | 115-199 |
| 0007 | 20 | GA | | | 14-0 | 28-42-11 | D01756 | 3 | | | D40002P | 1 | | | ALL |
| 0008 | 18 | GA | | | 2-0 | 28-42-11 | D01756 | 2 | 18 | | GD00170 | DC.. | E | | ALL |
| 0009 | 18 | GA | | | 2-0 | 28-42-11 | D01756 | 4 | 18 | | GD00171 | ST.. | E | | ALL |
| 0011R | 20 | QA | | | 22-0 | 26-11-11 | D42282P | 4 | | | D40014P | 4 | | | 001-099 |
| 0011R | 20 | QA | | | 21-0 | 26-11-11 | D42282P | 4 | | | D40014P | 4 | | | 115-199 |
| 0012R | 20 | QA | | | 22-0 | 26-11-11 | D42282P | 8 | | | D40014P | 8 | | | 001-099 |
| 0012R | 20 | QA | | | 21-0 | 26-11-11 | D42282P | 8 | | | D40014P | 8 | | | 115-199 |
| 0013R | 20 | QA | | | 22-0 | 26-11-11 | D42282P | 6 | | | D40014P | 6 | | | 001-099 |
| 0013R | 20 | QA | | | 21-0 | 26-11-11 | D42282P | 6 | | | D40014P | 6 | | | 115-199 |
| 0014 | 20 | GA | | | 22-0 | 29-22-11 | D42282P | 23 | | | D40002P | 53 | | | ALL |
| 0015 | 20 | GA | | | 22-0 | 29-22-11 | D42282P | 24 | | | D40002P | 54 | | | ALL |
| 0016 | 20 | GA | | | 22-0 | 29-22-11 | D42282P | 25 | | | D40002P | 55 | | | ALL |
| 0057 | 20 | GA | | | 22-0 | SPARE | D40014P | 11 | | | D42282P | 11 | | | 001-099 |
| 0057 | 20 | GA | | | 21-0 | SPARE | D40014P | 11 | | | D42282P | 11 | | | 115-199 |
| 0058 | 20 | GA | | | 22-0 | SPARE | D40014P | 12 | | | D42282P | 12 | | | 001-099 |
| 0058 | 20 | GA | | | 21-0 | SPARE | D40014P | 12 | | | D42282P | 12 | | | 115-199 |
| 0059 | 18 | GA | | | 22-0 | 26-18-11 | D40014P | 13 | | | D42282P | 14 | | | 001-099 |
| 0059 | 18 | GA | | | 21-0 | 26-18-11 | D40014P | 13 | | | D42282P | 14 | | | 115-199 |
| 0061 | 20 | GA | | | 22-0 | 29-11-11 | D40014P | 10 | | | D42282P | 10 | | | 001-099 |
| 0061 | 20 | GA | | | 21-0 | 29-11-11 | D40014P | 10 | | | D42282P | 10 | | | 115-199 |
| 0062 | 20 | GA | | | 22-0 | 29-11-11 | D40014P | 9 | | | D42282P | 13 | | | 001-099 |
| 0062 | 20 | GA | | | 21-0 | 29-11-11 | D40014P | 9 | | | D42282P | 13 | | | 115-199 |
| 0066 | 20 | GA | | | 22-0 | SPARE | D42280P | 6 | | | D40002P | 41 | | | 001-099 |
| 0067 | 20 | GA | | | 22-0 | 29-11-12 | D42280P | 7 | | | D40002P | 8 | | | 001-099 |
| 0067 | 20 | GA | | | 21-0 | 29-11-12 | D42280P | 7 | | | D40002P | 8 | | | 115-199 |
| 0072 | 20 | GA | | | 22-0 | 29-11-12 | D42280P | 8 | | | D40002P | 42 | | | 001-099 |
| 0072 | 20 | GA | | | 21-0 | 29-11-12 | D42280P | 8 | | | D40002P | 42 | | | 115-199 |
| 0080 | 20 | GA | | | 22-0 | 29-11-12 | D42280P | 11 | | | D40002P | 12 | | | 001-099 |
| 0080 | 20 | GA | | | 21-0 | 29-11-12 | D42280P | 11 | | | D40002P | 12 | | | 115-199 |
| 0082 | 20 | GA | | | 14-0 | 28-25-11 | D01756 | 1 | | | D40002P | 14 | | | ALL |
| 0085 | 20 | GA | | | 22-0 | 29-22-11 | D40002P | 35 | | | D42280P | 10 | | | 001-099 |
| 0085 | 20 | GA | | | 21-0 | 29-22-11 | D40002P | 35 | | | D42280P | 10 | | | 115-199 |
| 0094 | 20 | GA | | | 22-0 | SPARE | D40002P | 30 | | | D42280P | 27 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3300 | 286N3300 | | | | LEFT ENGINE STRUT TO LEFT FRONT/SPAR DISC (continued) | | | | | | | | | | | |
| 0095 | 20 | | GA | | 22-0 | SPARE | | D40002P | 29 | | | D42280P | 26 | | | 001-099 |
| 0096 | 20 | | GA | | 27-0 | 30-11-11 | | D00568 | 4 | | | D40002P | 46 | | | 001-099 |
| 0096 | 20 | | GA | | 28-0 | 30-11-11 | | D00568 | 4 | | | D40002P | 46 | | | 115-199 |
| 0097 | 20 | | GA | | 27-0 | 30-11-11 | | D00568 | 5 | | | D40002P | 47 | | | 001-099 |
| 0097 | 20 | | GA | | 28-0 | 30-11-11 | | D00568 | 5 | | | D40002P | 47 | | | 115-199 |
| 0098 | 20 | | GA | | 27-0 | 30-11-11 | | D00568 | 1 | | | D40002P | 48 | | | 001-099 |
| 0098 | 20 | | GA | | 28-0 | 30-11-11 | | D00568 | 1 | | | D40002P | 48 | | | 115-199 |
| 0099 | 20 | | GA | | 2-0 | 30-11-11 | | D00568 | 2 | | | GD01006 | DC.. | E | | ALL |
| 0100 | 20 | | GA | | 2-0 | 30-11-11 | | D00568 | 3 | | | GD01006 | DC.. | E | | ALL |
| 0101 | 18 | | GA | | 2-0 | 30-11-11 | | D00568 | 6 | | | GD01007 | ST.. | E | | ALL |
| 1001 | 18 | | GE | AP | 22-0 | 73-21-11 | | D40014P | 16 | | | D42282P | 16 | | | 001-099 |
| 1001 | 18 | | GE | AF | 21-0 | 73-21-11 | | D42282P | 16 | | | D40014P | 16 | | | 115-199 |
| 1001Z | | | | AP | 0-0 | 73-21-11 | | D40014P | S/R | | | D42282P | S/R | | | 001-099 |
| 1001Z | | | | AF | 0-0 | 73-21-11 | | D42282P | S/R | | | D40014P | S/R | | | 115-199 |
| 1002 | 20 | | GE | AS | 21-0 | 76-11-11 | | D42280P | 1 | | | D40002P | 11 | | | 001-099 |
| 1002 | 20 | | GE | AG | 21-0 | 76-11-11 | | D42280P | 1 | | | D40002P | 11 | | | 115-199 |
| 1002Z | | | | AS | 0-0 | 76-11-11 | | D42280P | S/R | | | D40002P | S/R | | | 001-099 |
| 1002Z | | | | AG | 0-0 | 76-11-11 | | D42280P | S/R | | | D40002P | S/R | | | 115-199 |
| 1003 | 20 | | GE | AV | 0-12 | 76-11-11 | | D42282P | 9 | | | SM00001 | | 9 | | 001-099 |
| 1003 | 20 | | GE | AK | 0-12 | 76-11-11 | | D42282P | 9 | | | SM00001 | | 9 | | 115-199 |
| 1003Z | | | | AV | 0-0 | 76-11-11 | | D42282P | S/R | | | SM00REF | 1 | | AC | 001-099 |
| 1003Z | | | | AK | 0-0 | 76-11-11 | | D42282P | S/R | | | SM00REF | 1 | | AA | 115-199 |
| 1004 | 20 | | GE | AW | 19-11 | 76-11-11 | | D40014P | 7 | | | SM00001 | | 9 | | 001-099 |
| 1004 | 20 | | GE | AZ | 21-0 | 76-11-11 | | D40014P | 7 | | | SM00001 | | 9 | | 115-199 |
| 1004Z | | | | AW | 0-0 | 76-11-11 | | D40014P | S/R | | | SM00REF | 1 | | AC | 001-099 |
| 1004Z | | | | AZ | 0-0 | 76-11-11 | | SM00REF | 1 | AA | | D40014P | S/R | | | 115-199 |
| 1005 | 20 | | GE | AX | 21-0 | 76-11-11 | | D40002P | 20 | | | SM00001 | | 9 | | 001-099 |
| 1005 | 20 | | GE | AM | 21-0 | 76-11-11 | | D40002P | 20 | | | SM00001 | | 9 | | 115-199 |
| 1005Z | | | | AX | 0-0 | 76-11-11 | | D40002P | S/R | | | SM00REF | 1 | | AC | 001-099 |
| 1005Z | | | | AM | 0-0 | 76-11-11 | | D40002P | S/R | | | SM00REF | 1 | | AA | 115-199 |
| 1006 | 20 | | GE | AB | 22-0 | SPARE | | D40002P | 21 | | | D42280P | 19 | | | 001-099 |
| 1006Z | | | | AB | 0-0 | SPARE | | D40002P | S/R | | | D42280P | S/R | | | 001-099 |
| 1007 | 18 | | GE | AC | 22-0 | 28-22-21 | | D40014P | 15 | | | D42280P | 9 | | | 001-099 |
| 1007 | 18 | | GE | AR | 21-0 | 28-22-21 | | D40014P | 15 | | | D42280P | 9 | | | 115-199 |
| 1007Z | | | | AC | 0-0 | 28-22-21 | | D40014P | S/R | | | D42280P | S/R | | | 001-099 |
| 1007Z | | | | AR | 0-0 | 28-22-21 | | D40014P | S/R | | | D42280P | S/R | | | 115-199 |
| 1008 | 20 | | GE | AD | 22-0 | SPARE | | D40002P | 13 | | | D42280P | 12 | | | 001-099 |
| 1008 | 20 | | GE | AS | 21-0 | 28-41-21 | | D40002P | 13 | | | D42280P | 12 | | | 115-199 |
| 1008Z | | | | AD | 0-0 | SPARE | | D40002P | S/R | | | D42280P | S/R | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3300 | | 286N3300 | | | | LEFT ENGINE STRUT TO LEFT FRONT/SPAR DISC (continued) | | | | | | | | | |
| 1008Z | | | | AS | 0-0 | 28-41-21 | D40002P | S/R | | | D42280P | S/R | | | 115-199 |
| 1009 | | 18 | HP | AZ | 3-0 | 26-18-11 | D40014P | 14 | | | D01952 | = 1 | | | 001-099 |
| 1009 | | 18 | HP | AT | 3-0 | 26-18-11 | D40014P | 14 | | | D01952 | = 1 | | | 115-199 |
| 1009Z | | | | AZ | 0-0 | 26-18-11 | D40014P | S/R | | | GD02699 | ST.. | E | | 001-099 |
| 1009Z | | | | AT | 0-0 | 26-18-11 | D40014P | S/R | | | GD02699 | ST.. | E | | 115-199 |
| 2501B | | 16 | GF | BA | 22-0 | 75-31-11 | D40014P | 3 | | | D42282P | 15 | | | 001-099 |
| 2501B | | 20 | GF | AA | 21-0 | 73-21-11 | D42280P | 5 | | | D40002P | 5 | | | 115-199 |
| 2501R | | 16 | GF | BA | 0-0 | 75-31-11 | D40014P | 17 | | | D42282P | 17 | | | 001-099 |
| 2501R | | 20 | GF | AA | 0-0 | 73-21-11 | D42280P | 15 | | | D40002P | 15 | | | 115-199 |
| 2501Z | | | | BA | 0-0 | 75-31-11 | D40014P | S/R | | | D42282P | S/R | | | 001-099 |
| 2501Z | | | | AA | 0-0 | 73-21-11 | D42280P | | | AD | D40002P | | | AE | 115-199 |
| 2502B | | 20 | GF | BD | 22-0 | 73-21-11 | D42280P | 16 | | | D40002P | 16 | | | 001-099 |
| 2502B | | 20 | GF | AB | 21-0 | 73-21-11 | D42280P | 16 | | | D40002P | 16 | | | 115-199 |
| 2502R | | 20 | GF | BD | 0-0 | 73-21-11 | D42280P | 17 | | | D40002P | 17 | | | 001-099 |
| 2502R | | 20 | GF | AB | 0-0 | 73-21-11 | D42280P | 17 | | | D40002P | 17 | | | 115-199 |
| 2502Z | | | | BD | 0-0 | 73-21-11 | D42280P | | | AD | D40002P | | | AE | 001-099 |
| 2502Z | | | | AB | 0-0 | 73-21-11 | D42280P | | | AD | D40002P | | | AE | 115-199 |
| 2503B | | 20 | GF | BE | 22-0 | 73-21-11 | D42280P | 31 | | | D40002P | 44 | | | 001-099 |
| 2503B | | 20 | GF | AC | 21-0 | 73-21-11 | D42280P | 31 | | | D40002P | 44 | | | 115-199 |
| 2503R | | 20 | GF | BE | 0-0 | 73-21-11 | D42280P | 32 | | | D40002P | 43 | | | 001-099 |
| 2503R | | 20 | GF | AC | 0-0 | 73-21-11 | D42280P | 32 | | | D40002P | 43 | | | 115-199 |
| 2503Z | | | | BE | 0-0 | 73-21-11 | D42280P | | | AD | D40002P | | | AE | 001-099 |
| 2503Z | | | | AC | 0-0 | 73-21-11 | D42280P | | | AD | D40002P | | | AE | 115-199 |
| 2504B | | 20 | GF | AT | 22-0 | 76-11-11 | D42282P | 3 | | | D40014P | 27 | | | 001-099 |
| 2504B | | 16 | GF | AH | 21-0 | 75-31-11 | D42282P | 15 | | | D40014P | 3 | | | 115-199 |
| 2504R | | 20 | GF | AT | 0-0 | 76-11-11 | D42282P | 7 | | | D40014P | 28 | | | 001-099 |
| 2504R | | 16 | GF | AH | 0-0 | 75-31-11 | D42282P | 17 | | | D40014P | 17 | | | 115-199 |
| 2504Z | | | | AT | 0-0 | 76-11-11 | D42282P | S/R | | | D40014P | S/R | | | 001-099 |
| 2504Z | | | | AH | 0-0 | 75-31-11 | D42282P | S/R | | | D40014P | S/R | | | 115-199 |
| 2505B | | 20 | GF | AJ | 21-0 | 76-11-11 | D42282P | 3 | | | D40014P | 27 | | | 115-199 |
| 2505R | | 20 | GF | AJ | 0-0 | 76-11-11 | D42282P | 7 | | | D40014P | 28 | | | 115-199 |
| 2505Z | | | | AJ | 0-0 | 76-11-11 | D42282P | S/R | | | D40014P | S/R | | | 115-199 |
| 2506B | | 20 | GF | AP | 21-0 | SPARE | D42280P | 4 | | | D40002P | 22 | | | 115-199 |
| 2506R | | 20 | GF | AP | 0-0 | SPARE | D42280P | 6 | | | D40002P | 41 | | | 115-199 |
| 2506Z | | | | AP | 0-0 | SPARE | D42280P | S/R | | | D40002P | S/R | | | 115-199 |
| 2510B | | 20 | GF | BF | 22-0 | 73-21-11 | D42280P | 5 | | | D40002P | 5 | | | 001-099 |
| 2510B | | 20 | GF | AN | 21-0 | SPARE | D40002P | 9 | | | D42280P | 2 | | | 115-199 |
| 2510R | | 20 | GF | BF | 0-0 | 73-21-11 | D42280P | 15 | | | D40002P | 15 | | | 001-099 |
| 2510R | | 20 | GF | AN | 0-0 | SPARE | D40002P | 10 | | | D42280P | 3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|------------------------|------------------------|-------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | Effectivity |
| W3300 | 286N3300 | LEFT ENGINE STRUT TO LEFT FRONT/SPAR DISC (continued) | | | |
| 2510Z | | BF 0-0 73-21-11 | D42280P AD | D40002P AE | 001-099 |
| 2510Z | | AN 0-0 SPARE | D40002P S/R | D42280P S/R | 115-199 |
| 2511B | 20 GF | BG 22-0 SPARE | D40002P 23 | D42280P 20 | 001-099 |
| 2511R | 20 GF | BG 0-0 SPARE | D40002P 24 | D42280P 21 | 001-099 |
| 2511Z | | BG 0-0 SPARE | D40002P 25 | D42280P 22 | 001-099 |
| 2512B | 20 GF | BH 22-0 SPARE | D40002P 26 | D42280P 23 | 001-099 |
| 2512R | 20 GF | BH 0-0 SPARE | D40002P 27 | D42280P 24 | 001-099 |
| 2512Z | | BH 0-0 SPARE | D40002P 28 | D42280P 25 | 001-099 |
| 3504B | 20 GG | AA 22-0 SPARE | D40002P 9 | D42280P 2 | 001-099 |
| 3504R | 20 GG | AA 0-0 SPARE | D40002P 10 | D42280P 3 | 001-099 |
| 3504Y | 20 GG | AA 0-0 SPARE | D40002P 22 | D42280P 4 | 001-099 |
| 3504Z | | AA 0-0 SPARE | D40002P S/R | D42280P S/R | 001-099 |
| 4501G | 20 DU | BB 22-0 75-31-11 | D40002P 33 TC | D42280P 33 4H | 001-099 |
| 4501G | 20 DU | AD 21-0 75-31-11 | D42280P 33 4H | D40002P 33 TC | 115-199 |
| 4501W | 20 DU | BB 0-0 75-31-11 | D40002P 34 TD | D42280P 34 4L | 001-099 |
| 4501W | 20 DU | AD 0-0 75-31-11 | D42280P 34 4L | D40002P 34 TD | 115-199 |
| 4501Z | | BB 0-0 75-31-11 | D40002P S/R | D42280P S/R | 001-099 |
| 4501Z | | AD 0-0 75-31-11 | D42280P S/R | D40002P S/R | 115-199 |
| 4502G | 20 DU | BC 22-0 77-21-11 | D40002P 3 TC | D42280P 35 4H | 001-099 |
| 4502G | 20 DU | AE 21-0 77-21-11 | D42280P 35 4H | D40002P 3 TC | 115-199 |
| 4502W | 20 DU | BC 0-0 77-21-11 | D40002P 4 TD | D42280P 36 4L | 001-099 |
| 4502W | 20 DU | AE 0-0 77-21-11 | D42280P 36 4L | D40002P 4 TD | 115-199 |
| 4502Z | | BC 0-0 77-21-11 | D40002P S/R | D42280P S/R | 001-099 |
| 4502Z | | AE 0-0 77-21-11 | D42280P S/R | D40002P S/R | 115-199 |
| FRAD | | 0-0 73-21-11 | D42280P AD | D42280P 30 | ALL |
| FRAE | | 0-0 73-21-11 | D40002P AE | D40002P 45 | ALL |
| YAAA | | 0-0 76-11-11 | GD03025 ST.. E * | D40002P S/R | ALL |
| YAAB | | 0-0 26-13-11 | GD03025 ST.. E * | D40014P S/R | ALL |
| W3301 | 286N3301 | L. WHEEL WELL/SPOILER DISC. PNL TO SPOILER #1- CHANNEL L2A | | | |
| 0001 | 20 GA | 1-7 27-61-13 | D00641 10 | GD00557 ST.. E | ALL |
| 4501RB | 20 7N | AA 46-9 27-61-13 | D40573J 7 | D00641 7 | ALL |
| 4501WB | 20 7N | AA 0-0 27-61-13 | D40573J 3 | D00641 1 | ALL |
| 4501WK | 20 7N | AA 0-0 27-61-13 | D40573J 8 | D00641 8 | ALL |
| 4501WN | 20 7N | AA 0-0 27-61-13 | D40573J 6 | D00641 6 | ALL |
| 4501WO | 20 7N | AA 0-0 27-61-13 | D40573J 5 | D00641 5 | ALL |
| 4501WR | 20 7N | AA 0-0 27-61-13 | D40573J 1 | D00641 3 | ALL |
| 4501WV | 20 7N | AA 0-0 27-61-13 | D40573J 9 | D00641 9 | ALL |
| 4501Z | | AA 0-0 27-61-13 | D40573J S/R | GD00557 ST.. E | ALL |

WIRE LIST

D280N032

91-21-11
Section W3300
Page 4
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3302 | | 286N3302 | | | | LEFT ENGINE STRUT TO LEFT FRONT SPAR DISC | | | | | | | | | |
| 0004 | 18 | GA | | | 20-10 | 26-18-11 | D40006P | | 8 | | D42276J | 26 | | | ALL |
| 0006 | 18 | GA | | | 20-10 | 29-32-11 | D40006P | | 10 | | D42276J | 1 | | | ALL |
| 0017 | 20 | GA | | | 20-10 | 78-36-11 | D40006P | | 34 | | D42276J | 8 | | | ALL |
| 0018 | 20 | GA | | | 20-10 | 78-36-11 | D40006P | | 35 | | D42276J | 9 | | | ALL |
| 0020 | 20 | GA | | | 20-10 | 76-11-11 | D40006P | | 36 | | D42276J | 10 | | | ALL |
| 0021 | 20 | GA | | | 20-10 | 76-11-11 | D40006P | | 37 | | D42276J | 11 | | | ALL |
| 0035 | 20 | GA | | | 20-10 | SPARE | D40006P | | 1 | | D42276J | 32 | | | 115-199 |
| 0037 | 20 | GA | | | 20-10 | 78-36-11 | D40006P | | 33 | | D42276J | 29 | | | 003-099 |
| 1001 | 18 | HP | AL | | 3-1 | 26-18-11 | D40006P | | 9 | | D01948 | = 1 | | | ALL |
| 1001Z | | | AL | | 0-0 | 26-18-11 | D40006P | S/R | | | GD02699 | ST.. | E | | ALL |
| 1002 | 20 | GE | T | | 20-10 | 76-11-21 | D40006P | | 19 | | D42276J | 7 | | | ALL |
| 1002Z | | | T | | 0-0 | 76-11-21 | D40006P | S/R | | | D42276J | S/R | | | ALL |
| 2501B | 20 | GF | AF | | 20-10 | 79-34-11 | D40006P | | 31 | | D42276J | 15 | | | ALL |
| 2501R | 20 | GF | AF | | 0-0 | 79-34-11 | D40006P | | 32 | | D42276J | 16 | | | ALL |
| 2501Z | | | AF | | 0-0 | 79-34-11 | D40006P | S/R | | | D42276J | S/R | | | ALL |
| 2502B | 20 | GF | AG | | 20-10 | 79-34-11 | D40006P | | 5 | | D42276J | 27 | | | ALL |
| 2502R | 20 | GF | AG | | 0-0 | 79-34-11 | D40006P | | 6 | | D42276J | 28 | | | ALL |
| 2502Z | | | AG | | 0-0 | 79-34-11 | D40006P | S/R | | | D42276J | S/R | | | ALL |
| 2503B | 20 | GF | AH | | 20-10 | 74-31-11 | D40006P | | 17 | | D42276J | 5 | | | ALL |
| 2503R | 20 | GF | AH | | 0-0 | 74-31-11 | D40006P | | 18 | | D42276J | 6 | | | ALL |
| 2503Z | | | AH | | 0-0 | 74-31-11 | D40006P | S/R | | | D42276J | S/R | | | ALL |
| 2504B | 20 | GF | AA | | 20-10 | SPARE | D40006P | | 1 | | D42276J | 32 | | | 001-099 |
| 2504R | 20 | GF | AA | | 0-0 | SPARE | D40006P | | 2 | | D42276J | 33 | | | 001-099 |
| 2504Z | | | AA | | 0-0 | SPARE | D40006P | | 4 | | D42276J | 35 | | | 001-099 |
| 2505B | 20 | GF | AM | | 20-10 | SPARE | D40006P | | 2 | | D42276J | 33 | | | 115-199 |
| 2505R | 20 | GF | AM | | 0-0 | SPARE | D40006P | | 3 | | D42276J | 34 | | | 115-199 |
| 2505Z | | | AM | | 0-0 | SPARE | D40006P | | 4 | | D42276J | 35 | | | 115-199 |
| 3502B | 20 | GG | AJ | | 20-10 | 30-21-11 | D40006P | | 11 | | D42276J | 2 | | | ALL |
| 3502R | 20 | GG | AJ | | 0-0 | 30-21-11 | D40006P | | 12 | | D42276J | 3 | | | ALL |
| 3502Y | 20 | GG | AJ | | 0-0 | 30-21-11 | D40006P | | 13 | | D42276J | 4 | | | ALL |
| 3502Z | | | AJ | | 0-0 | 30-21-11 | D40006P | S/R | | | D42276J | S/R | | | ALL |
| 3503B | 20 | GG | AB | | 20-10 | 73-31-11 | D40006P | | 15 | | D42276J | 19 | | | ALL |
| 3503R | 20 | GG | AB | | 0-0 | 73-31-11 | D40006P | | 14 | | D42276J | 18 | | | ALL |
| 3503Y | 20 | GG | AB | | 0-0 | 73-31-11 | D40006P | | 16 | | D42276J | 17 | | | ALL |
| 3503Z | | | AB | | 0-0 | 73-31-11 | D40006P | S/R | | | D42276J | S/R | | | ALL |
| 3504B | 20 | GG | AD | | 20-10 | 79-31-11 | D40006P | | 26 | | D42276J | 20 | | | ALL |
| 3504R | 20 | GG | AD | | 0-0 | 79-31-11 | D40006P | | 27 | | D42276J | 21 | | | ALL |
| 3504Y | 20 | GG | AD | | 0-0 | 79-31-11 | D40006P | | 25 | | D42276J | 22 | | | ALL |
| 3504Z | | | AD | | 0-0 | 79-31-11 | D40006P | S/R | | | D42276J | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3302 | 286N3302 | | | LEFT ENGINE STRUT TO LEFT FRONT SPAR DISC (continued) | | | | | | | | | | | |
| 3505B | 20 | GG | AE | | 20-10 | 79-32-11 | D40006P | 28 | | | D42276J | 23 | | | ALL |
| 3505R | 20 | GG | AE | | 0-0 | 79-32-11 | D40006P | 29 | | | D42276J | 24 | | | ALL |
| 3505Y | 20 | GG | AE | | 0-0 | 79-32-11 | D40006P | 30 | | | D42276J | 25 | | | ALL |
| 3505Z | | | AE | | 0-0 | 79-32-11 | D40006P | S/R | | | D42276J | S/R | | | ALL |
| 3506B | 20 | GG | AK | | 20-10 | SPARE | D40006P | 40 | | | D42276J | 12 | | | ALL |
| 3506R | 20 | GG | AK | | 0-0 | SPARE | D40006P | 41 | | | D42276J | 13 | | | ALL |
| 3506Y | 20 | GG | AK | | 0-0 | SPARE | D40006P | 42 | | | D42276J | 14 | | | ALL |
| 3506Z | | | AK | | 0-0 | SPARE | D40006P | S/R | | | D42276J | S/R | | | ALL |
| YAAA | | | | | 0-0 | 29-32-11 | GD03017 | ST.. | E | | D40006P | S/R | | | 001-099 |
| YAAA | | | | | 0-0 | 73-31-11 | GD03017 | ST.. | E | | D40006P | S/R | | | 115-199 |
| W3304 | 286N3304 | | | LEFT ENGINE STRUT TO LEFT FRONT SPAR DISC | | | | | | | | | | | |
| 0001 | 20 | GA | | | 2-0 | 77-31-11 | D42272P | 7 | | | D42272P | 8 | | | ALL |
| 0002 | 20 | GA | | | 2-0 | 77-31-11 | D42272P | 18 | | | D42272P | 34 | | | ALL |
| 0003 | 20 | GA | | | 2-0 | 77-31-11 | D42272P | 21 | | | D42272P | 39 | | | ALL |
| 0004 | 20 | GA | | | 2-0 | 77-31-11 | D40018P | 22 | | | D40018P | 39 | | | ALL |
| 0006 | 20 | GA | | | 2-0 | 77-31-11 | D40018P | 11 | | | D40018P | 26 | | | ALL |
| 0007 | 20 | GA | | | 2-0 | 77-31-11 | D40018P | 10 | | | D40018P | 9 | | | ALL |
| 0008 | 20 | GA | | | 21-0 | SPARE | D42272P | 6 | | | D40018P | 15 | | | 001-099 |
| 0009 | 20 | GA | | | 21-0 | SPARE | D42272P | 9 | | | D40018P | 18 | | | 001-099 |
| 0010 | 20 | GA | | | 21-0 | SPARE | D40018P | 15 | | | D42272P | 5 | | | 115-199 |
| 1003 | 20 | GE | T | | 21-0 | 77-11-11 | D40018P | 3 | | | D42272P | 3 | | | ALL |
| 1003Z | | | T | | 0-0 | 77-11-11 | D40018P | S/R | | | D42272P | S/R | | | ALL |
| 2001B | 18 | GB | AE | | 21-0 | 22-33-11 | D40018P | 14 | | | D42272P | 13 | | | ALL |
| 2001R | 18 | GB | AE | | 0-0 | 22-33-11 | D40018P | 16 | | | D42272P | 14 | | | ALL |
| 2002B | 18 | GB | AF | | 21-0 | 22-33-11 | D40018P | 35 | | | D42272P | 15 | | | ALL |
| 2002R | 18 | GB | AF | | 0-0 | 22-33-11 | D40018P | 6 | | | D42272P | 16 | | | ALL |
| 2501B | 20 | GF | AD | | 21-0 | 77-12-31 | D40018P | 30 | | | D42272P | 31 | | | ALL |
| 2501R | 20 | GF | AD | | 0-0 | 77-12-31 | D40018P | 29 | | | D42272P | 32 | | | ALL |
| 2501Z | | | AD | | 0-0 | 77-12-31 | D40018P | S/R | | | D42272P | S/R | | | ALL |
| 2502B | 20 | GF | AN | | 21-0 | SPARE | D40018P | 18 | | | D42272P | 6 | | | 115-199 |
| 2502R | 20 | GF | AN | | 0-0 | SPARE | D40018P | 32 | | | D42272P | 28 | | | 115-199 |
| 2502Z | | | AN | | 0-0 | SPARE | D40018P | S/R | | | D42272P | S/R | | | 115-199 |
| 2503B | 18 | GF | AP | | 21-0 | 73-21-12 | D40018P | 8 | | | D42272P | 10 | | | 001-099 |
| 2503B | 18 | GF | AH | | 21-0 | 73-21-12 | D40018P | 8 | | | D42272P | 10 | | | 115-199 |
| 2503R | 18 | GF | AP | | 0-0 | 73-21-12 | D40018P | 7 | | | D42272P | 11 | | | 001-099 |
| 2503R | 18 | GF | AH | | 0-0 | 73-21-12 | D40018P | 7 | | | D42272P | 11 | | | 115-199 |
| 2503Z | | | AP | | 0-0 | 73-21-12 | D40018P | S/R | | | D42272P | S/R | | | 001-099 |
| 2503Z | | | AH | | 0-0 | 73-21-12 | D40018P | S/R | | | D42272P | S/R | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3304 | 286N3304 | | | LEFT ENGINE STRUT TO LEFT FRONT SPAR DISC (continued) | | | | | | | | | | | |
| 2504B | 20 | GF | AK | | 21-0 | 75-31-11 | D40018P | 1 | | | D42272P | 1 | | | ALL |
| 2504R | 20 | GF | AK | | 0-0 | 75-31-11 | D40018P | 13 | | | D42272P | 4 | | | ALL |
| 2504Z | | | AK | | 0-0 | 75-31-11 | D40018P | S/R | | | D42272P | S/R | | | ALL |
| 2505B | 16 | GF | AJ | | 21-0 | 75-31-11 | D40018P | 31 | | | D42272P | 2 | | | ALL |
| 2505R | 16 | GF | AJ | | 0-0 | 75-31-11 | D40018P | 33 | | | D42272P | 12 | | | ALL |
| 2505Z | | | AJ | | 0-0 | 75-31-11 | D40018P | S/R | | | D42272P | S/R | | | ALL |
| 2506B | 18 | GF | AM | | 21-0 | 73-21-11 | D40018P | 2 | | | D42272P | 29 | | | 115-199 |
| 2506R | 18 | GF | AM | | 0-0 | 73-21-11 | D40018P | 34 | 18 | | D42272P | 9 | | | 115-199 |
| 2506Z | | | AM | | 0-0 | 73-21-11 | D40018P | S/R | | | D42272P | S/R | | | 115-199 |
| 2507B | 18 | GF | BA | | 21-0 | 73-21-11 | D40018P | 2 | | | D42272P | 29 | | | 001-099 |
| 2507B | 20 | GF | AP | | 21-0 | SPARE | D40018P | 38 | | | D42272P | 25 | | | 115-199 |
| 2507R | 18 | GF | BA | | 0-0 | 73-21-11 | D40018P | 34 | | | D42272P | 30 | | | 001-099 |
| 2507R | 20 | GF | AP | | 0-0 | SPARE | D40018P | 19 | | | D42272P | 26 | | | 115-199 |
| 2507Z | | | BA | | 0-0 | 73-21-11 | D40018P | S/R | | | D42272P | S/R | | | 001-099 |
| 2507Z | | | AP | | 0-0 | SPARE | D40018P | S/R | | | D42272P | S/R | | | 115-199 |
| 2508B | 20 | GF | BC | | 21-0 | SPARE | D42272P | 26 | | | D40018P | 17 | | | 001-099 |
| 2508R | 20 | GF | BC | | 0-0 | SPARE | D42272P | 25 | | | D40018P | 19 | | | 001-099 |
| 2508Z | | | BC | | 0-0 | SPARE | D42272P | S/R | | | D40018P | S/R | | | 001-099 |
| 2509B | 20 | GF | BD | | 21-0 | SPARE | D42272P | 5 | | | D40018P | 20 | | | 001-099 |
| 2509R | 20 | GF | BD | | 0-0 | SPARE | D42272P | 27 | | | D40018P | 21 | | | 001-099 |
| 2509Z | | | BD | | 0-0 | SPARE | D42272P | S/R | | | D40018P | S/R | | | 001-099 |
| 4501R | 20 | RJ | AB | | 21-0 | 77-31-11 | D40018P | 40 | | | D42272P | 19 | | | ALL |
| 4501W | 20 | RJ | AB | | 0-0 | 77-31-11 | D40018P | 25 | | | D42272P | 35 | | | ALL |
| 4501Z | | | AB | | 0-0 | 77-31-11 | D40018P | 23 | | | D42272P | 20 | | | ALL |
| 4502R | 20 | RJ | AC | | 21-0 | 77-31-11 | D40018P | 42 | | | D42272P | 36 | | | ALL |
| 4502W | 20 | RJ | AC | | 0-0 | 77-31-11 | D40018P | 41 | | | D42272P | 37 | | | ALL |
| 4502Z | | | AC | | 0-0 | 77-31-11 | D40018P | 24 | | | D42272P | 38 | | | ALL |
| 5001B | 20 | GF | AA | | 21-0 | 77-11-11 | D40018P | 4 | | | D42272P | 40 | | | ALL |
| 5001R | 20 | GF | AA | | 0-0 | 77-11-11 | D40018P | 5 | | | D42272P | 22 | | | ALL |
| 5001Z | | | AA | | 0-0 | 77-11-11 | D40018P | S/R | | | D42272P | S/R | | | ALL |
| 5002B | 20 | GF | AR | | 21-0 | 77-11-11 | D40018P | 36 | | | D42272P | 23 | | | 001-099 |
| 5002B | 20 | GF | AG | | 21-0 | 77-11-11 | D40018P | 36 | | | D42272P | 23 | | | 115-199 |
| 5002R | 20 | GF | AR | | 0-0 | 77-11-11 | D40018P | 37 | | | D42272P | 24 | | | 001-099 |
| 5002R | 20 | GF | AG | | 0-0 | 77-11-11 | D40018P | 37 | | | D42272P | 24 | | | 115-199 |
| 5002Z | | | AR | | 0-0 | 77-11-11 | D40018P | S/R | | | D42272P | S/R | | | 001-099 |
| 5002Z | | | AG | | 0-0 | 77-11-11 | D40018P | S/R | | | D42272P | S/R | | | 115-199 |
| YAAA | | | | | 0-0 | 77-11-11 | D40018P | S/R | | | GD03106 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 7

May 17/2006



WIRE LIST
D280N032

91-21-11
Section W3300
Page 8
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|----------|--|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3306 | | 286N3306 | | | | | LEFT REAR SPAR DISC TO FUEL & FLIGHT CONTROLS (continued) | | | | | | | | |
| 1019 | 18 | GE | BC | | 2-9 | 28-42-11 | D01758 | 3 | 18 | | D40898J | 20 | 18 | | 001-099 |
| 1019 | 18 | GE | BC | | 2-9 | 28-42-11 | D01758 | 3 | 18 | | D40898P | 20 | 18 | | 115-199 |
| 1019Z | | | BC | | 0-0 | 28-42-11 | GD01863 | ST.. | E | *1 | D40898J | S/R | | | 001-099 |
| 1019Z | | | BC | | 0-0 | 28-42-11 | GD01863 | ST.. | E | *1 | D40898P | S/R | | | 115-199 |
| 1020 | 20 | GE | BF | | 46-1 | 27-18-11 | D40898J | 36 | | | D02104 | 3 | | | 001-099 |
| 1020 | 20 | GE | BF | | 46-1 | 27-18-11 | D40898P | 36 | | | D02104 | 3 | | | 115-199 |
| 1020Z | | | BF | | 0-0 | 27-18-11 | D40898J | S/R | | | GD02326 | ST.. | E | | 001-099 |
| 1020Z | | | BF | | 0-0 | 27-18-11 | D40898P | S/R | | | GD02326 | ST.. | E | | 115-199 |
| 2501B | 20 | 2Z | AI | | 48-10 | 28-21-21 | D02510 | B | | | D40898J | 9 | | | 001-099 |
| 2501B | 20 | 2Z | AI | | 48-10 | 28-21-21 | D02510 | B | | | D40898P | 9 | | | 115-199 |
| 2501R | 20 | 2Z | AI | | 0-0 | 28-21-21 | D02510 | A | | | D40898J | 8 | | | 001-099 |
| 2501R | 20 | 2Z | AI | | 0-0 | 28-21-21 | D02510 | A | | | D40898P | 8 | | | 115-199 |
| 2501ZI | | | AI | | 0-0 | 28-21-21 | D02510 | C | | | D40898J | 10 | | | 001-099 |
| 2501ZI | | | AI | | 0-0 | 28-21-21 | D02510 | C | | | D40898P | 10 | | | 115-199 |
| 2501ZO | | | AI | | 0-0 | 28-21-21 | GD00263 | ST.. | E | | D40898J | S/R | | | 001-099 |
| 2501ZO | | | AI | | 0-0 | 28-21-21 | GD00263 | ST.. | E | | D40898P | S/R | | | 115-199 |
| 2502B | 20 | GF | AC | | 46-1 | 27-18-11 | D02104 | 4 | | | D40898J | 6 | | | 001-099 |
| 2502B | 20 | GF | AC | | 46-1 | 27-18-11 | D02104 | 4 | | | D40898P | 6 | | | 115-199 |
| 2502R | 20 | GF | AC | | 0-0 | 27-18-11 | D02104 | 5 | | | D40898J | 7 | | | 001-099 |
| 2502R | 20 | GF | AC | | 0-0 | 27-18-11 | D02104 | 5 | | | D40898P | 7 | | | 115-199 |
| 2502Z | | | AC | | 0-0 | 27-18-11 | GD02326 | ST.. | E | *1 | D40898J | S/R | | | 001-099 |
| 2502Z | | | AC | | 0-0 | 27-18-11 | GD02326 | ST.. | E | *1 | D40898P | S/R | | | 115-199 |
| 2504B | 20 | GF | AG | | 10-3 | 28-41-21 | D02790 | 3 | | | D40898P | 2 | | | 115-199 |
| 2504R | 20 | GF | AG | | 0-0 | 28-41-21 | D02790 | 4 | | | D40898P | 1 | | | 115-199 |
| 2504Z | | | AG | | 0-0 | 28-41-21 | GD00997 | ST.. | E | *1 | D40898P | S/R | | | 115-199 |
| 2505B | 20 | GF | AH | | 10-3 | 28-41-21 | D02790 | 6 | | | D40898P | 4 | | | 115-199 |
| 2505R | 20 | GF | AH | | 0-0 | 28-41-21 | D02790 | 7 | | | D40898P | 3 | | | 115-199 |
| 2505Z | | | AH | | 0-0 | 28-41-21 | GD00997 | ST.. | E | *1 | D40898P | S/R | | | 115-199 |
| 2509B | 20 | GF | AK | | 9-8 | 28-21-23 | D02500 | 2 | | | D40898J | 12 | | | 001-099 |
| 2509B | 20 | GF | AK | | 9-8 | 28-21-23 | D02500 | 2 | 16 | * | D40898J | 12 | | | 010-099 |
| 2509B | 20 | GF | AK | | 9-8 | 28-21-23 | D02500 | 2 | | | D40898P | 12 | | | 115-199 |
| 2509R | 20 | GF | AK | | 0-0 | 28-21-23 | D02500 | 5 | | | D40898J | 11 | | | 001-099 |
| 2509R | 20 | GF | AK | | 0-0 | 28-21-23 | D02500 | 5 | | | D40898P | 11 | | | 115-199 |
| 2509Z | | | AK | | 0-0 | 28-21-23 | GD00999 | ST.. | E | | D40898J | S/R | | | 001-099 |
| 2509Z | | | AK | | 0-0 | 28-21-23 | GD00999 | ST.. | E | | D40898P | S/R | | | 115-199 |
| 2510B | 20 | GF | AM | | 42-5 | 27-51-61 | D01702 | 13 | | | D40922J | 2 | | | 001-099 |
| 2510B | 20 | GF | AM | | 42-5 | 27-51-61 | D01702 | 13 | | | D40922P | 2 | | | 115-199 |
| 2510R | 20 | GF | AM | | 0-0 | 27-51-61 | D01702 | 12 | | | D40922J | 1 | | | 001-099 |
| 2510R | 20 | GF | AM | | 0-0 | 27-51-61 | D01702 | 12 | | | D40922P | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3306 | 286N3306 | LEFT REAR SPAR DISC TO FUEL & FLIGHT CONTROLS (continued) | | | | | | | | | | | | | |
| 2510Z | | AM | 0-0 | 27-51-61 | GD02325 | ST.. | E | *1 | D40922J | S/R | | | 001-099 | | |
| 2510Z | | AM | 0-0 | 27-51-61 | GD02325 | ST.. | E | *1 | D40922P | S/R | | | 115-199 | | |
| 2511B | 20 | GF AB | 40-7 | 27-51-41 | D01702 | 7 | | | D40898J | 16 | | | 001-099 | | |
| 2511B | 20 | GF AB | 40-7 | 27-51-41 | D01702 | 7 | | | D40898P | 16 | | | 115-199 | | |
| 2511R | 20 | GF AB | 0-0 | 27-51-41 | D01702 | 6 | | | D40898J | 15 | | | 001-099 | | |
| 2511R | 20 | GF AB | 0-0 | 27-51-41 | D01702 | 6 | | | D40898P | 15 | | | 115-199 | | |
| 2511Z | | AB | 0-0 | 27-51-41 | GD02325 | ST.. | E | *1 | D40898J | S/R | | | 001-099 | | |
| 2511Z | | AB | 0-0 | 27-51-41 | GD02325 | ST.. | E | *1 | D40898P | S/R | | | 115-199 | | |
| 3001B | 18 | GC BE | 5-0 | 28-22-11 | SP05012 | 9 | | | D01764 | 3 | | | ALL | | |
| 3001R | 18 | GC BE | 0-0 | 28-22-11 | SP05008 | 9 | | | D01764 | 1 | | | ALL | | |
| 3001Y | 18 | GC BE | 0-0 | 28-22-11 | SP05010 | 9 | | | D01764 | 2 | | | ALL | | |
| 3501B | 20 | GG AL | 40-7 | 27-58-11 | D01702 | 1 | | | D40898J | 18 | | | 001-099 | | |
| 3501B | 20 | GG AL | 40-7 | 27-58-11 | D01702 | 1 | | | D40898P | 18 | | | 115-199 | | |
| 3501R | 20 | GG AL | 0-0 | 27-58-11 | D01702 | 2 | | | D40898J | 17 | | | 001-099 | | |
| 3501R | 20 | GG AL | 0-0 | 27-58-11 | D01702 | 2 | | | D40898P | 17 | | | 115-199 | | |
| 3501Y | 20 | GG AL | 0-0 | 27-58-11 | D01702 | 3 | | | D40898J | 19 | | | 001-099 | | |
| 3501Y | 20 | GG AL | 0-0 | 27-58-11 | D01702 | 3 | | | D40898P | 19 | | | 115-199 | | |
| 3501Z | | AL | 0-0 | 27-58-11 | GD02325 | ST.. | E | *1 | D40898J | S/R | | | 001-099 | | |
| 3501Z | | AL | 0-0 | 27-58-11 | GD02325 | ST.. | E | *1 | D40898P | S/R | | | 115-199 | | |
| 3502B | 20 | GG BD | 12-5 | 28-22-21 | D40902J | 2 | | | D02142 | 2 | | | 001-099 | | |
| 3502B | 20 | GG BD | 12-5 | 28-22-21 | D40902P | 2 | | | D02142 | 2 | | | 115-199 | | |
| 3502R | 20 | GG BD | 0-0 | 28-22-21 | D40902J | 3 | | | D02142 | 5 | | | 001-099 | | |
| 3502R | 20 | GG BD | 0-0 | 28-22-21 | D40902P | 3 | | | D02142 | 5 | | | 115-199 | | |
| 3502Y | 20 | GG BD | 0-0 | 28-22-21 | D40902J | 1 | | | D02142 | 3 | | | 001-099 | | |
| 3502Y | 20 | GG BD | 0-0 | 28-22-21 | D40902P | 1 | | | D02142 | 3 | | | 115-199 | | |
| 3502Z | | BD | 0-0 | 28-22-21 | D40902J | S/R | | | GD02319 | ST.. | E | | 001-099 | | |
| 3502Z | | BD | 0-0 | 28-22-21 | D40902P | S/R | | | GD02319 | ST.. | E | | 115-199 | | |
| 3503B | 20 | GG AE | 4-1 | 28-26-11 | D01522 | 5 | | | D40898J | 13 | | | 001-099 | | |
| 3503B | 20 | GG AE | 4-1 | 28-26-11 | D01522 | 5 | | | D40898P | 13 | | | 115-199 | | |
| 3503R | 20 | GG AE | 0-0 | 28-26-11 | D01522 | 3 | | | D40898J | 14 | | | 001-099 | | |
| 3503R | 20 | GG AE | 0-0 | 28-26-11 | D01522 | 3 | | | D40898P | 14 | | | 115-199 | | |
| 3503Y | 20 | GG AE | 0-0 | 28-26-11 | D01522 | 2 | | | D40898J | 21 | | | 001-099 | | |
| 3503Y | 20 | GG AE | 0-0 | 28-26-11 | D01522 | 2 | | | D40898P | 21 | | | 115-199 | | |
| 3503Z | | AE | 0-0 | 28-26-11 | GD00994 | ST.. | E | | D40898J | S/R | | | 001-099 | | |
| 3503Z | | AE | 0-0 | 28-26-11 | GD00994 | ST.. | E | | D40898P | S/R | | | 115-199 | | |
| 4251B | 20 | GH AA | 40-7 | 27-51-41 | D01702 | 9 | | | D40898J | 23 | | | 001-099 | | |
| 4251B | 20 | GH AA | 40-7 | 27-51-41 | D01702 | 9 | | | D40898P | 23 | | | 115-199 | | |
| 4251G | 20 | GH AA | 0-0 | 27-51-41 | D01702 | 11 | | | D40898J | 25 | | | 001-099 | | |
| 4251G | 20 | GH AA | 0-0 | 27-51-41 | D01702 | 11 | | | D40898P | 25 | | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | Effectivity | |
|---|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|-------------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3306 | | | | | | | | | | | | | | | |
| 286N3306 | | | | | | | | | | | | | | | |
| LEFT REAR SPAR DISC TO FUEL & FLIGHT CONTROLS (continued) | | | | | | | | | | | | | | | |
| 4251R | 20 | | GH | AA | 0-0 | 27-51-41 | D01702 | 8 | | | D40898J | 22 | | | 001-099 |
| 4251R | 20 | | GH | AA | 0-0 | 27-51-41 | D01702 | 8 | | | D40898P | 22 | | | 115-199 |
| 4251Y | 20 | | GH | AA | 0-0 | 27-51-41 | D01702 | 10 | | | D40898J | 24 | | | 001-099 |
| 4251Y | 20 | | GH | AA | 0-0 | 27-51-41 | D01702 | 10 | | | D40898P | 24 | | | 115-199 |
| 4251Z | | | | AA | 0-0 | 27-51-41 | GD02325 | ST.. | E | *2 | D40898J | S/R | | | 001-099 |
| 4251Z | | | | AA | 0-0 | 27-51-41 | GD02325 | ST.. | E | *2 | D40898P | S/R | | | 115-199 |
| 4252B | 20 | | GH | AN | 42-5 | 27-51-61 | D01702 | 15 | | | D40922J | 4 | | | 001-099 |
| 4252B | 20 | | GH | AN | 42-5 | 27-51-61 | D01702 | 15 | | | D40922P | 4 | | | 115-199 |
| 4252G | 20 | | GH | AN | 0-0 | 27-51-61 | D01702 | 17 | | | D40922J | 6 | | | 001-099 |
| 4252G | 20 | | GH | AN | 0-0 | 27-51-61 | D01702 | 17 | | | D40922P | 6 | | | 115-199 |
| 4252R | 20 | | GH | AN | 0-0 | 27-51-61 | D01702 | 14 | | | D40922J | 3 | | | 001-099 |
| 4252R | 20 | | GH | AN | 0-0 | 27-51-61 | D01702 | 14 | | | D40922P | 3 | | | 115-199 |
| 4252Y | 20 | | GH | AN | 0-0 | 27-51-61 | D01702 | 16 | | | D40922J | 5 | | | 001-099 |
| 4252Y | 20 | | GH | AN | 0-0 | 27-51-61 | D01702 | 16 | | | D40922P | 5 | | | 115-199 |
| 4252Z | | | | AN | 0-0 | 27-51-61 | GD02325 | ST.. | E | *2 | D40922J | S/R | | | 001-099 |
| 4252Z | | | | AN | 0-0 | 27-51-61 | GD02325 | ST.. | E | *2 | D40922P | S/R | | | 115-199 |
| T-B | | | | | 0-0 | 28-21-23 | R10409 | BLU | | | GD00996 | DC.. | E | | 010-099 |
| T-R | | | | | 0-0 | 28-21-23 | R10409 | RED | | | D02500 | 2 | 16 | * | 010-099 |
| W-B | | | | | 0-0 | SPARE | R10409 | CAP | Y | | R10409 | BLU | | | 010-099 |
| W-R | | | | | 0-0 | SPARE | R10409 | CAP | Y | | R10409 | RED | | | 010-099 |
| W3309 | | | | | | | | | | | | | | | |
| 286N3309 | | | | | | | | | | | | | | | |
| L. WHEEL WELL/SPOILER DISC. PNL TO SPOILER #6-CHANNEL L2B | | | | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 2-0 | 27-61-18 | D00651 | 10 | | | GD00577 | ST.. | E | | ALL |
| 4501RB | 20 | | 7N | AA | 24-0 | 27-61-18 | D40581J | 7 | | | D00651 | 7 | | | 001-099 |
| 4501RB | 20 | | 7N | AA | 23-0 | 27-61-18 | D40581J | 7 | | | D00651 | 7 | | | 115-199 |
| 4501WB | 20 | | 7N | AA | 0-0 | 27-61-18 | D40581J | 3 | | | D00651 | 1 | | | ALL |
| 4501WK | 20 | | 7N | AA | 0-0 | 27-61-18 | D40581J | 8 | | | D00651 | 8 | | | ALL |
| 4501WN | 20 | | 7N | AA | 0-0 | 27-61-18 | D40581J | 6 | | | D00651 | 6 | | | ALL |
| 4501WO | 20 | | 7N | AA | 0-0 | 27-61-18 | D40581J | 5 | | | D00651 | 5 | | | ALL |
| 4501WR | 20 | | 7N | AA | 0-0 | 27-61-18 | D40581J | 1 | | | D00651 | 3 | | | ALL |
| 4501WV | 20 | | 7N | AA | 0-0 | 27-61-18 | D40581J | 9 | | | D00651 | 9 | | | ALL |
| 4501Z | | | | AA | 0-0 | 27-61-18 | D40581J | S/R | | | GD00577 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3300

Page 11 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| | | | | | | | | | | | | | | | |
| W3311 | 286N3311 | | | L. SPOILER/SPAR DISC PNL TO SPOILER #2-CHANNEL R2A | | | | | | | | | | | |
| 0001 | 20 | | GA | | 2-0 | 27-61-14 | D00643 | 10 | | | GD00561 | ST.. | E | | ALL |
| 4501RB | 20 | | 7N | AA | 46-0 | 27-61-14 | D40505J | 7 | | | D00643 | 7 | | | 001-099 |
| 4501RB | 20 | | 7N | AA | 46-0 | 27-61-14 | D40505P | 7 | | | D00643 | 7 | | | 115-199 |
| 4501WB | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505J | 3 | | | D00643 | 1 | | | 001-099 |
| 4501WB | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505P | 3 | | | D00643 | 1 | | | 115-199 |
| 4501WK | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505J | 8 | | | D00643 | 8 | | | 001-099 |
| 4501WK | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505P | 8 | | | D00643 | 8 | | | 115-199 |
| 4501WN | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505J | 6 | | | D00643 | 6 | | | 001-099 |
| 4501WN | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505P | 6 | | | D00643 | 6 | | | 115-199 |
| 4501WO | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505J | 5 | | | D00643 | 5 | | | 001-099 |
| 4501WO | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505P | 5 | | | D00643 | 5 | | | 115-199 |
| 4501WR | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505J | 1 | | | D00643 | 3 | | | 001-099 |
| 4501WR | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505P | 1 | | | D00643 | 3 | | | 115-199 |
| 4501WV | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505J | 9 | | | D00643 | 9 | | | 001-099 |
| 4501WV | 20 | | 7N | AA | 0-0 | 27-61-14 | D40505P | 9 | | | D00643 | 9 | | | 115-199 |
| 4501Z | | | | AA | 0-0 | 27-61-14 | D40505J | S/R | | | GD00561 | ST.. | E | | 001-099 |
| 4501Z | | | | AA | 0-0 | 27-61-14 | D40505P | S/R | | | GD00561 | ST.. | E | | 115-199 |
| | | | | | | | | | | | | | | | |
| W3312 | 286N3312 | | | L ENG F/W DISC TO P31 PANEL, GENERATOR FEEDERS | | | | | | | | | | | |
| 0001 | *2 | | 43 | | 63-9 | 24-21-11 | C00901 | T1 | H* | | SM00001 | | GX | | 001-099 |
| 0001 | *2 | | 43 | | 64-0 | 24-21-11 | C00901 | T1 | H* | | SM00001 | | GX | | 115-199 |
| 0002 | *2 | | 43 | | 63-9 | 24-21-11 | C00901 | T2 | H* | | SM00002 | | GX | | 001-099 |
| 0002 | *2 | | 43 | | 64-0 | 24-21-11 | C00901 | T2 | H* | | SM00002 | | GX | | 115-199 |
| 0003 | *2 | | 43 | | 63-9 | 24-21-11 | C00901 | T3 | H* | | SM00003 | | GX | | 001-099 |
| 0003 | *2 | | 43 | | 64-0 | 24-21-11 | C00901 | T3 | H* | | SM00003 | | GX | | 115-199 |
| 0004 | *1 | | CQ | | 13-0 | 24-21-11 | SM00004 | | GX | | D01116P | A | | | ALL |
| 0005 | *1 | | CQ | | 13-0 | 24-21-11 | SM00005 | | GX | | D01116P | B | | | ALL |
| 0006 | *1 | | CQ | | 13-0 | 24-21-11 | SM00006 | | GX | | D01116P | C | | | ALL |
| 0007 | 04 | | CQ | | 3-10 | 24-21-11 | GD00240 | AC.. | H7 | | D01116P | D | | | 001-099 |
| 0007 | 04 | | CQ | | 3-7 | 24-21-11 | GD00240 | AC.. | H7 | | D01116P | D | | | 115-199 |
| 0008 | *2 | | 43 | | 1-5 | 24-21-11 | SM00001 | | GX | | SM00004 | | GX | | 001-099 |
| 0008 | *2 | | 43 | | 1-6 | 24-21-11 | SM00001 | | GX | | SM00004 | | GX | | 115-199 |
| 0009 | *2 | | 43 | | 1-5 | 24-21-11 | SM00002 | | GX | | SM00005 | | GX | | 001-099 |
| 0009 | *2 | | 43 | | 1-6 | 24-21-11 | SM00002 | | GX | | SM00005 | | GX | | 115-199 |
| 0010 | *2 | | 43 | | 1-5 | 24-21-11 | SM00003 | | GX | | SM00006 | | GX | | 001-099 |
| 0010 | *2 | | 43 | | 1-6 | 24-21-11 | SM00003 | | GX | | SM00006 | | GX | | 115-199 |
| | | | | | | | | | | | | | | | |
| W3314 | 286N3314 | | | L. W/B DISC TO L. ENG F/W - L. ENG/GEN CONTROL | | | | | | | | | | | |
| 0001 | 20 | | GA | | 20-6 | 24-11-11 | D40288P | 8 | | | D40024J | 8 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3310

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3314 | 286N3314 | | | L. W/B DISC TO L. ENG F/W - L. ENG/GEN CONTROL (continued) | | | | | | | | | | | |
| 0002 | 16 | | GA | | 20-6 | 24-11-11 | D40288P | 4 | 16 | | D40024J | 4 | | | ALL |
| 0006 | 20 | | GA | | 20-6 | SPARE | D40288P | 25 | | | D40024J | 25 | | | ALL |
| 0007 | 20 | | GA | | 20-6 | SPARE | D40288P | 26 | | | D40024J | 26 | | | ALL |
| 2001B | 20 | | GB | AD | 20-6 | 24-11-11 | D40288P | 19 | | | D40024J | 19 | | | ALL |
| 2001R | 20 | | GB | AD | 0-0 | 24-11-11 | D40288P | 18 | | | D40024J | 18 | | | ALL |
| 2002B | 20 | | GB | AE | 20-6 | 24-11-11 | D40288P | 7 | | | D40024J | 7 | | | ALL |
| 2002R | 20 | | GB | AE | 0-0 | 24-11-11 | D40288P | 6 | | | D40024J | 6 | | | ALL |
| 2003B | 20 | | GB | AG | 20-6 | SPARE | D40288P | 22 | | | D40024J | 22 | | | ALL |
| 2003R | 20 | | GB | AG | 0-0 | SPARE | D40288P | 23 | | | D40024J | 23 | | | ALL |
| 2501B | 20 | | GF | AB | 20-6 | 24-21-11 | D40288P | 10 | | | D40024J | 10 | | | ALL |
| 2501R | 20 | | GF | AB | 0-0 | 24-21-11 | D40288P | 9 | | | D40024J | 9 | | | ALL |
| 2501Z | | | | AB | 0-0 | 24-21-11 | D40288P | 11 | | | D40024J | 11 | | | ALL |
| 2502B | 20 | | GF | AF | 20-6 | 24-11-11 | D40288P | 2 | | | D40024J | 2 | | | ALL |
| 2502R | 20 | | GF | AF | 0-0 | 24-11-11 | D40288P | 1 | | | D40024J | 1 | | | ALL |
| 2502Z | | | | AF | 0-0 | 24-11-11 | D40288P | 5 | | | D40024J | 5 | | | ALL |
| 3001B | 18 | | GC | AA | 20-6 | 24-21-11 | D40288P | 16 | 18 | | D40024J | 16 | | | ALL |
| 3001R | 18 | | GC | AA | 0-0 | 24-21-11 | D40288P | 15 | 18 | | D40024J | 15 | | | ALL |
| 3001Y | 18 | | GC | AA | 0-0 | 24-21-11 | D40288P | 17 | 18 | | D40024J | 17 | | | ALL |
| 4001B | 20 | | GD | AC | 20-6 | 24-21-11 | D40288P | 13 | | | D40024J | 13 | | | ALL |
| 4001G | 20 | | GD | AC | 0-0 | 24-21-11 | D40288P | 3 | | | D40024J | 3 | | | ALL |
| 4001R | 20 | | GD | AC | 0-0 | 24-21-11 | D40288P | 12 | | | D40024J | 12 | | | ALL |
| 4001Y | 20 | | GD | AC | 0-0 | 24-21-11 | D40288P | 14 | | | D40024J | 14 | | | ALL |
| YAAA | | | | | 0-0 | 24-11-11 | D40288P | S/R | | | GD03025 | ST.. | E | | ALL |
| W3315 | 286N3315 | | | L. SPOILER/SPAR DISC. PNL TO SPOILER #3-CHANNEL R2C | | | | | | | | | | | |
| 0001 | 20 | | GA | | 2-0 | 27-61-15 | D00645 | 10 | | | GD00565 | ST.. | E | | ALL |
| 4501RB | 20 | | 7N | AA | 34-0 | 27-61-15 | D40529J | 7 | | | D00645 | 7 | | | 001-099 |
| 4501RB | 20 | | 7N | AA | 33-0 | 27-61-15 | D40529P | 7 | | | D00645 | 7 | | | 115-199 |
| 4501WB | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529J | 3 | | | D00645 | 1 | | | 001-099 |
| 4501WB | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529P | 3 | | | D00645 | 1 | | | 115-199 |
| 4501WK | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529J | 8 | | | D00645 | 8 | | | 001-099 |
| 4501WK | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529P | 8 | | | D00645 | 8 | | | 115-199 |
| 4501WN | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529J | 6 | | | D00645 | 6 | | | 001-099 |
| 4501WN | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529P | 6 | | | D00645 | 6 | | | 115-199 |
| 4501WO | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529J | 5 | | | D00645 | 5 | | | 001-099 |
| 4501WO | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529P | 5 | | | D00645 | 5 | | | 115-199 |
| 4501WR | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529J | 1 | | | D00645 | 3 | | | 001-099 |
| 4501WR | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529P | 1 | | | D00645 | 3 | | | 115-199 |
| 4501WV | 20 | | 7N | AA | 0-0 | 27-61-15 | D40529J | 9 | | | D00645 | 9 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3310

Page 2

May 17/2006



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3319 | 286N3319 | | | L. AFT BODY/SPAR DISC TO SPOILER #4-CHANNEL R2B (continued) | | | | | | | | | | | |
| 4501WO | 20 | 7N | AA | | 0-0 | 27-61-16 | D40543P | | 5 | | D00647 | | 5 | | 115-199 |
| 4501WR | 20 | 7N | AA | | 0-0 | 27-61-16 | D40543J | | 1 | | D00647 | | 3 | | 001-099 |
| 4501WR | 20 | 7N | AA | | 0-0 | 27-61-16 | D40543P | | 1 | | D00647 | | 3 | | 115-199 |
| 4501WV | 20 | 7N | AA | | 0-0 | 27-61-16 | D40543J | | 9 | | D00647 | | 9 | | 001-099 |
| 4501WV | 20 | 7N | AA | | 0-0 | 27-61-16 | D40543P | | 9 | | D00647 | | 9 | | 115-199 |
| 4501Z | | | AA | | 0-0 | 27-61-16 | D40543J | | S/R | | GD00569 | ST.. | E | | 001-099 |
| 4501Z | | | AA | | 0-0 | 27-61-16 | D40543P | | S/R | | GD00569 | ST.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3310

Page 4 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|---|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| Wire No. | | | | | | | | | | | | | | | | | |
| W3320 | 286N3320 | | | | LEFT STRUT DISC TO LEFT FRONT/SPAR DISC - T/R CONTROL | | | | | | | | | | | | |
| 0001 | 20 | | GK | | 29-7 | 36-11-11 | | D40026P | 7 | | | D40012P | 7 | | | ALL | |
| 0002 | 20 | | GK | | 24-6 | 26-11-12 | | D40026P | 8 | | | D41162P | 5 | | | ALL | |
| 0003 | 20 | | GK | | 24-6 | 26-11-12 | | D40026P | 12 | | | D41162P | 2 | | | ALL | |
| 0004 | 18 | | GK | | 1-2 | 26-12-11 | | S10197 | =2 | C | | GD00229 | DC.. | E | | ALL | |
| 0005 | 18 | | GK | | 25-10 | 26-12-11 | | D40026P | 10 | | | S10197 | =1 | C | * | ALL | |
| 0006 | 18 | | GK | | 5-2 | 26-12-11 | | S10198 | =2 | C | | GD00248 | DC.. | E | | ALL | |
| 0007 | 18 | | GK | | 4-5 | 26-12-11 | | S10197 | =1 | C | * | S10198 | =1 | C | * | ALL | |
| 0008 | 18 | | GK | | 10-7 | 26-12-11 | | D41162P | 3 | | | S10198 | =1 | C | * | ALL | |
| 0009 | 18 | | GK | | 24-6 | 26-12-11 | | D41162P | 4 | | | D40026P | 11 | | | ALL | |
| 2001B | 20 | | GL | AA | 29-7 | 78-34-11 | | D40026P | 2 | | | D40012P | 2 | | | ALL | |
| 2001R | 20 | | GL | AA | 0-0 | 78-34-11 | | D40026P | 1 | | | D40012P | 1 | | | ALL | |
| 2002B | 20 | | GL | AB | 29-7 | 78-34-11 | | D40026P | 4 | | | D40012P | 4 | | | ALL | |
| 2002R | 20 | | GL | AB | 0-0 | 78-34-11 | | D40026P | 3 | | | D40012P | 3 | | | ALL | |
| 2003B | 20 | | GL | AC | 29-7 | SPARE | | D40026P | 6 | | | D40012P | 6 | | | ALL | |
| 2003R | 20 | | GL | AC | 0-0 | SPARE | | D40026P | 5 | | | D40012P | 5 | | | ALL | |
| YAAA | | | | | 0-0 | 78-34-11 | | D40026P | S/R | | | GD03106 | ST.. | E | | ALL | |
| W3322 | 286N3322 | | | | LEFT STRUT DISC TO LEFT FRONT/SPAR DISC - T/R INDICATION | | | | | | | | | | | | |
| 2001B | 20 | | GL | AA | 26-11 | 78-36-11 | | D40268P | 2 | | | D40266P | 2 | | | ALL | |
| 2001R | 20 | | GL | AA | 0-0 | 78-36-11 | | D40268P | 1 | | | D40266P | 1 | | | ALL | |
| 2002B | 20 | | GL | AB | 26-11 | 78-36-11 | | D40268P | 4 | | | D40266P | 4 | | | ALL | |
| 2002R | 20 | | GL | AB | 0-0 | 78-36-11 | | D40268P | 3 | | | D40266P | 3 | | | ALL | |
| 2003B | 20 | | GL | AC | 26-11 | 78-36-11 | | D40268P | 6 | | | D40266P | 6 | | | ALL | |
| 2003R | 20 | | GL | AC | 0-0 | 78-36-11 | | D40268P | 5 | | | D40266P | 5 | | | ALL | |
| 2004B | 20 | | GL | AD | 26-11 | 78-36-11 | | D40268P | 8 | | | D40266P | 8 | | | ALL | |
| 2004R | 20 | | GL | AD | 0-0 | 78-36-11 | | D40268P | 7 | | | D40266P | 7 | | | ALL | |
| 2501B | 16 | | HQ | MN | 27-3 | 78-34-51 | | D41448P | 4 | | | D40266P | 10 | | | ALL | |
| 2501R | 16 | | HQ | MN | 0-0 | 78-34-51 | | D41448P | 3 | | | D40266P | 9 | | | ALL | |
| 2501Z | | | | MN | 0-0 | 78-34-51 | | D41448P | 5 | | | D40266P | S/R | | | ALL | |
| YAAA | | | | | 0-0 | 78-36-11 | | D40268P | S/R | | | GD03025 | ST.. | E | | ALL | |
| YBBB | | | | | 0-0 | 78-34-51 | | D41448P | S/R | | | GD03017 | ST.. | E | | ALL | |
| W3326 | 286N3326 | | | | VAPOR BARRIER TO WING TIP-LEFT | | | | | | | | | | | | |
| 0002 | 16 | | GA | | 0-4 | 33-43-11 | | SM00009 | | 9 | | D41392J | 8 | | | ALL | |
| 0007 | 18 | | GA | | 2-0 | 33-44-21 | | D00018 | 3 | | | GD01238 | ST.. | E | | ALL | |
| 0008 | 18 | | GA | | 2-0 | 27-51-41 | | D02984 | 13 | | | GD01590 | ST.. | E | | ALL | |
| 0014 | 18 | | GA | | 0-8 | 33-43-11 | | SP01872 | REF | | FB | GD01228 | ST.. | E | | ALL | |
| 1001 | 20 | | GE | AA | 30-0 | 27-81-31 | | SP01112 | | 9 | | D41392J | 11 | | | ALL | |
| 1001Z | | | | AA | 0-0 | 27-81-31 | | GD01667 | DC.. | E | | D41392J | S/R | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W3320

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|---|-------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3326 | 286N3326 | VAPOR BARRIER TO WING TIP-LEFT (continued) | | | | | | | | | | | | | |
| 2506B | 12 | HF | AF | 50-0 | 33-43-11 | SM00009 | | 9 | SP01874 | | 9 | | ALL | | |
| 2506R | 12 | HF | AF | 0-0 | 33-43-11 | GD01231 | AC.. | E | SP01872 | | 9 | | ALL | | |
| 2506Z | | | AF | 0-0 | 33-43-11 | D41392J | S/R | | SP01872 | REF | | FB | ALL | | |
| 2509B | 18 | GF | AR | 52-0 | 33-44-21 | D00018 | 1 | | D41392J | 10 | | | ALL | | |
| 2509R | 18 | GF | AR | 0-0 | 33-44-21 | D00018 | 2 | | GD01860 | AC.. | E | | ALL | | |
| 2509Z | | | AR | 0-0 | 33-44-21 | GD01238 | ST.. | E | D41392J | S/R | | | ALL | | |
| 2510B | 20 | GF | AL | 48-0 | 27-51-41 | D02984 | 2 | | D41392J | 3 | | | ALL | | |
| 2510R | 20 | GF | AL | 0-0 | 27-51-41 | D02984 | 1 | | D41392J | 2 | | | ALL | | |
| 2510Z | | | AL | 0-0 | 27-51-41 | GD01590 | ST.. | E | D41392J | S/R | | | ALL | | |
| 2511B | 20 | GF | AN | 48-0 | 27-51-61 | D02984 | 8 | | D40304J | 4 | | | ALL | | |
| 2511R | 20 | GF | AN | 0-0 | 27-51-61 | D02984 | 7 | | D40304J | 3 | | | ALL | | |
| 2511Z | | | AN | 0-0 | 27-51-61 | GD01590 | ST.. | E | D40304J | S/R | | | ALL | | |
| 4251B | 20 | GH | AM | 50-0 | 27-51-41 | D02984 | 4 | | D41392J | 5 | | | ALL | | |
| 4251G | 20 | GH | AM | 0-0 | 27-51-41 | D02984 | 6 | | D41392J | 7 | | | ALL | | |
| 4251R | 20 | GH | AM | 0-0 | 27-51-41 | D02984 | 3 | | D41392J | 4 | | | ALL | | |
| 4251Y | 20 | GH | AM | 0-0 | 27-51-41 | D02984 | 5 | | D41392J | 6 | | | ALL | | |
| 4251Z | | | AM | 0-0 | 27-51-41 | GD01590 | ST.. | E | D41392J | S/R | | | ALL | | |
| 4252B | 20 | GH | AP | 48-0 | 27-51-61 | D02984 | 10 | | D41192J | 17 | | | ALL | | |
| 4252G | 20 | GH | AP | 0-0 | 27-51-61 | D02984 | 12 | | D41192J | 19 | | | ALL | | |
| 4252R | 20 | GH | AP | 0-0 | 27-51-61 | D02984 | 9 | | D41192J | 16 | | | ALL | | |
| 4252Y | 20 | GH | AP | 0-0 | 27-51-61 | D02984 | 11 | | D41192J | 18 | | | ALL | | |
| 4252Z | | | AP | 0-0 | 27-51-61 | GD01590 | ST.. | E | D41192J | S/R | | | ALL | | |
| 4501AA | 20 | 4K | AT | 2-0 | SPARE | D02788 | 13 | | D41192J | 14 | | | 115-199 | | |
| 4501RB | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 4 | | D41192J | 5 | | | 115-199 | | |
| 4501RG | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 3 | | D41192J | 4 | | | 115-199 | | |
| 4501RK | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 2 | | D41192J | 3 | | | 115-199 | | |
| 4501RV | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 6 | | D41192J | 7 | | | 115-199 | | |
| 4501RY | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 1 | | D41192J | 2 | | | 115-199 | | |
| 4501W | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 16 | | D41192J | 1 | | | 115-199 | | |
| 4501WB | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 12 | | D41192J | 13 | | | 115-199 | | |
| 4501WG | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 11 | | D41192J | 12 | | | 115-199 | | |
| 4501WK | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 5 | | D41192J | 6 | | | 115-199 | | |
| 4501WN | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 7 | | D41192J | 8 | | | 115-199 | | |
| 4501WO | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 10 | | D41192J | 11 | | | 115-199 | | |
| 4501WR | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 8 | | D41192J | 9 | | | 115-199 | | |
| 4501WV | 20 | 4K | AT | 0-0 | SPARE | D02788 | 14 | | D41192J | 15 | | | 115-199 | | |
| 4501WY | 20 | 4K | AT | 0-0 | 28-41-21 | D02788 | 9 | | D41192J | 10 | | | 115-199 | | |
| 4501Z | | | AT | 0-0 | 28-41-21 | GD01859 | ST.. | E | D41192J | S/R | | | 115-199 | | |
| A-A | | | | 0-0 | 33-44-21 | L00020 | J3 | | M00588 | J2 | | | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W3320

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3326 | 286N3326 | | | VAPOR BARRIER TO WING TIP-LEFT (continued) | | | | | | | | | | | |
| A-B | | | | | 0-0 | 27-81-31 | S10341 | | 3 | | SP01112 | CAP | Y | | ALL |
| A-C | | | | | 0-0 | 27-81-31 | S10341 | | 1 | | GD01667 | DC.. | E | | ALL |
| A-D | | | | | 0-0 | 27-81-31 | S10341 | | 2 | | SP01112 | | 9 | | ALL |
| W3328 | 286N3328 | | | L.W\B DISC TO L.STRUT | | | | | | | | | | | |
| 0001 | 18 | | HL | | 25-7 | 26-12-11 | D40042P | | 3 | | S10194 | =1 | C | * | ALL |
| 0002 | 18 | | HL | | 6-11 | 26-12-11 | S10194 | | =2 | C | GD00248 | DC.. | E | | ALL |
| 0003 | 18 | | HL | | 3-10 | 26-12-11 | S10194 | | =1 | C | S10195 | =1 | C | * | ALL |
| 0004 | 18 | | HL | | 1-6 | 26-12-11 | S10195 | | =2 | C | GD00229 | DC.. | E | | ALL |
| 0005 | 18 | | HL | | 6-11 | 26-12-11 | D40044P | | 1 | | S10195 | =1 | C | * | ALL |
| 0006 | 18 | | HL | | 24-0 | 26-12-11 | D40044P | | 2 | | D40042P | | 4 | | ALL |
| 0007 | 20 | | HL | | 24-0 | 26-11-12 | D40042P | | 6 | | D40044P | | 8 | | ALL |
| 0008 | 20 | | HL | | 24-0 | 26-11-12 | D40042P | | 2 | | D40044P | | 4 | | ALL |
| 0009 | 20 | | HL | | 24-3 | 36-11-11 | D40044P | | 5 | | D41208P | | 1 | | ALL |
| 0010 | 20 | | HL | | 24-3 | 36-11-11 | D40044P | | 6 | | D41208P | | 2 | | ALL |
| 0011 | 20 | | HL | | 24-3 | 36-11-11 | D40044P | | 7 | | D41208P | | 3 | | ALL |
| 0012 | 20 | | HL | | 24-3 | 36-11-12 | D40044P | | 3 | | D41208P | | 4 | | ALL |
| 0013 | 20 | | HL | | 24-3 | 36-11-12 | D40044P | | 9 | | D41208P | | 5 | | ALL |
| 0014 | 20 | | HL | | 24-3 | 36-11-12 | D40044P | | 10 | | D41208P | | 6 | | ALL |
| 0015 | 20 | | HL | | 24-3 | 36-11-12 | D40044P | | 11 | | D41208P | | 7 | | ALL |
| 0016 | 18 | | HL | | 24-3 | SPARE | D40044P | | 12 | | D41208P | | 8 | | ALL |
| 0017 | 18 | | HL | | 24-3 | SPARE | D40044P | | 13 | | D41208P | | 9 | | ALL |
| 0018 | 20 | | HL | | 24-0 | SPARE | D40042P | | 5 | | D40044P | | 14 | | ALL |
| 0019 | 18 | | HL | | 1-7 | 36-22-21 | GD02332 | DC.. | E | | SM00001 | | 9 | | ALL |
| 0020 | 20 | | HL | | 1-5 | 36-22-21 | D04702 | | B | | SM00001 | | 9 | | ALL |
| 2001B | 20 | | HM | AA | 23-11 | 36-22-21 | D04702 | | A | | D41208P | | 12 | | ALL |
| 2001R | 20 | | HM | AA | 0-0 | 36-22-21 | SM00001 | | | 9 | D41208P | | 13 | | ALL |
| YAAA | | | | | 0-0 | 26-12-11 | D40042P | | S/R | | GD03025 | ST.. | E | * | ALL |
| YAAB | | | | | 0-0 | 36-11-11 | D41208P | | S/R | | GD03025 | ST.. | E | * | ALL |

WIRE LIST

D280N032

91-21-11

Section W3320

Page 3 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3330 | 286N3330 | | | L. STRUT TO BLEED AIR VALVE | | | | | | | | | | | |
| 0001 | 18 | | 7A | | 3-0 | 26-12-11 | D40044J | | 1 | | S10196 | = 1 | L | * | ALL |
| 0002 | 18 | | 7A | | 3-0 | 26-12-11 | D40044J | | 2 | | S10196 | = 1 | L | * | ALL |
| 0003 | 18 | | 7A | | 3-0 | 26-12-11 | S10196 | = 2 | L | | GD00233 | DC.. | N | | ALL |
| 0004 | 20 | | 7A | | 4-2 | 26-11-12 | D40044J | | 8 | | D40816J | 5 | | | ALL |
| 0005 | 20 | | 7A | | 4-2 | 26-11-12 | D40044J | | 4 | | D40816J | 2 | | | ALL |
| 0006 | 18 | | 7A | | 2-5 | 36-11-11 | D40044J | | 5 | | D01644 | 7 | | | ALL |
| 0007 | 18 | | 7A | | 2-5 | 36-11-11 | D40044J | | 6 | | D01644 | 5 | | | ALL |
| 0008 | 18 | | 7A | | 2-5 | 36-11-11 | D40044J | | 7 | | D01644 | 2 | | | ALL |
| 0009 | 18 | | 7A | | 1-3 | 36-11-11 | D01644 | | 3 | | GD01554 | DC.. | N | | ALL |
| 0010 | 18 | | 7A | | 1-3 | 36-11-11 | D01644 | | 1 | | GD01554 | DC.. | N | | ALL |
| 0011 | 20 | | 7A | | 4-2 | 36-11-12 | D40044J | | 3 | | D40816J | 3 | | | ALL |
| 0012 | 20 | | 7A | | 4-2 | 36-11-12 | D40044J | | 9 | | D40816J | 4 | | | ALL |
| 0013 | 20 | | 7A | | 4-2 | 36-11-12 | D40044J | | 10 | | D40816J | 1 | | | ALL |
| 0014 | 20 | | 7A | | 4-2 | 36-11-12 | D40044J | | 11 | | D40816J | 6 | | | ALL |
| 0015 | 20 | | 7A | | 4-2 | SPARE | D40044J | | 14 | | D40816J | 7 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3330

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3342 | 286N3342 | | | | L. WING/BODY DISC. TO VAPOR SEAL- FLIGHT CONT & ANTI-ICE | | | | | | | | | | | |
| 0001 | 14 | | HA | | 7-5 | 27-81-11 | | D40076P | 15 | | | D01708 | 1 | | | ALL |
| 0002 | 14 | | HA | | 7-5 | 27-81-11 | | D40076P | 19 | | | D01708 | 2 | | | ALL |
| 0003 | 14 | | HA | | 7-5 | 27-81-11 | | D40076P | 23 | | | D01708 | 3 | | | ALL |
| 0004 | 16 | | GA | | 4-5 | 27-81-11 | | D01708 | 8 | | | GD01008 | ST.. | E | | ALL |
| 0005 | 20 | | GA | | 7-5 | 27-51-21 | | D40076P | 13 | | | D01708 | 7 | | | ALL |
| 0006 | 20 | | GA | | 7-5 | 27-51-21 | | D01708 | 6 | | | D40076P | 1 | | | ALL |
| 0019 | 18 | | GA | | 1-10 | 27-81-11 | | D01712 | 7 | | | GD01008 | ST.. | E | | ALL |
| 0020 | 18 | | GA | | 2-4 | 27-81-21 | | D03050 | 5 | | | GD01008 | ST.. | E | | ALL |
| 0021 | 20 | | GA | | 9-0 | 27-81-21 | | D03050 | 2 | | | D40076P | 24 | | | ALL |
| 0022 | 20 | | GA | | 9-0 | 27-81-21 | | D03050 | 1 | | | D40076P | 25 | | | ALL |
| 0023 | 20 | | GA | | 9-1 | 27-81-21 | | D03050 | 4 | | | D41394P | 25 | | | ALL |
| 0024 | 20 | | GA | | 9-1 | 27-81-21 | | D03050 | 3 | | | D41394P | 26 | | | ALL |
| 0026 | 18 | | HL | | 1-9 | 28-22-11 | | D01762 | 4 | | | GD01651 | ST.. | E | | ALL |
| 0027 | 20 | | GA | | 25-5 | SPARE | | D40304P | 1 | | | D40076P | 16 | | | ALL |
| 0028 | 20 | | GA | | 25-5 | SPARE | | D40304P | 2 | | | D40076P | 11 | | | ALL |
| 0035 | 20 | | GA | | 25-6 | SPARE | | D40304P | 11 | | | D41394P | 22 | | | ALL |
| 2001B | 20 | | GB | AA | 9-3 | 27-81-11 | | D40076P | 3 | | | D01712 | 2 | | | ALL |
| 2001R | 20 | | GB | AA | 0-0 | 27-81-11 | | D40076P | 2 | | | D01712 | 1 | | | ALL |
| 2002B | 20 | | GB | AB | 25-6 | 27-51-61 | | D40304P | 4 | | | D41394P | 21 | | | ALL |
| 2002R | 20 | | GB | AB | 0-0 | 27-51-61 | | D40304P | 3 | | | D41394P | 20 | | | ALL |
| 3001B | 18 | | HN | AF | 11-8 | 28-22-11 | | D01762 | 3 | | | SP05006 | | 9 | | ALL |
| 3001R | 18 | | HN | AF | 0-0 | 28-22-11 | | D01762 | 1 | | | SP05002 | | 9 | | ALL |
| 3001Y | 18 | | HN | AF | 0-0 | 28-22-11 | | D01762 | 2 | | | SP05004 | | 9 | | ALL |
| 4001B | 20 | | GD | AC | 9-3 | 27-81-11 | | D40076P | 5 | | | D01712 | 4 | | | ALL |
| 4001G | 20 | | GD | AC | 0-0 | 27-81-11 | | D40076P | 12 | | | D01712 | 6 | | | ALL |
| 4001R | 20 | | GD | AC | 0-0 | 27-81-11 | | D40076P | 4 | | | D01712 | 3 | | | ALL |
| 4001Y | 20 | | GD | AC | 0-0 | 27-81-11 | | D40076P | 6 | | | D01712 | 5 | | | ALL |
| 4002B | 20 | | HT | AD | 25-5 | 27-51-61 | | D41192P | 17 | | | D41394P | 17 | | | ALL |
| 4002G | 20 | | HT | AD | 0-0 | 27-51-61 | | D41192P | 19 | | | D41394P | 19 | | | ALL |
| 4002R | 20 | | HT | AD | 0-0 | 27-51-61 | | D41192P | 16 | | | D41394P | 16 | | | ALL |
| 4002Y | 20 | | HT | AD | 0-0 | 27-51-61 | | D41192P | 18 | | | D41394P | 18 | | | ALL |
| 4501AA | 20 | | 4K | AE | 25-5 | SPARE | | D41192P | 14 | | | D41394P | 14 | | | 115-199 |
| 4501RB | 20 | | 4K | AE | 0-0 | 28-41-21 | | D41192P | 5 | | | D41394P | 5 | | | 115-199 |
| 4501RG | 20 | | 4K | AE | 0-0 | 28-41-21 | | D41192P | 4 | | | D41394P | 4 | | | 115-199 |
| 4501RK | 20 | | 4K | AE | 0-0 | 28-41-21 | | D41192P | 3 | | | D41394P | 3 | | | 115-199 |
| 4501RV | 20 | | 4K | AE | 0-0 | 28-41-21 | | D41192P | 7 | | | D41394P | 7 | | | 115-199 |
| 4501RY | 20 | | 4K | AE | 0-0 | 28-41-21 | | D41192P | 2 | | | D41394P | 2 | | | 115-199 |
| 4501W | 20 | | 4K | AE | 0-0 | 28-41-21 | | D41192P | 1 | | | D41394P | 1 | | | 115-199 |
| 4501WB | 20 | | 4K | AE | 0-0 | 28-41-21 | | D41192P | 13 | | | D41394P | 13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3340

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|---|-------|---------|----------|---------|------|--------|---------|------|------|--------|-------------|---------|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3342 | 286N3342 | L. WING/BODY DISC. TO VAPOR SEAL- FLIGHT CONT & ANTI-ICE (continued) | | | | | | | | | | | | | |
| 4501WG | 20 | 4K | AE | 0-0 | 28-41-21 | D41192P | 12 | | D41394P | 12 | | | | 115-199 | |
| 4501WK | 20 | 4K | AE | 0-0 | 28-41-21 | D41192P | 6 | | D41394P | 6 | | | | 115-199 | |
| 4501WN | 20 | 4K | AE | 0-0 | 28-41-21 | D41192P | 8 | | D41394P | 8 | | | | 115-199 | |
| 4501WO | 20 | 4K | AE | 0-0 | 28-41-21 | D41192P | 11 | | D41394P | 11 | | | | 115-199 | |
| 4501WR | 20 | 4K | AE | 0-0 | 28-41-21 | D41192P | 9 | | D41394P | 9 | | | | 115-199 | |
| 4501WV | 20 | 4K | AE | 0-0 | SPARE | D41192P | 15 | | D41394P | 15 | | | | 115-199 | |
| 4501WY | 20 | 4K | AE | 0-0 | 28-41-21 | D41192P | 10 | | D41394P | 10 | | | | 115-199 | |
| 4501Z | | | AE | 0-0 | 28-41-21 | D41192P | S/R | | D41394P | S/R | | | | 115-199 | |
| YAAA | | | | 0-0 | 27-81-11 | D40076P | S/R | | GD03017 | ST.. | E | * | | ALL | |
| YAAB | | | | 0-0 | 28-22-11 | GD03017 | ST.. | E | SP05002 | DED | | | | ALL | |
| W3346 | 286N3346 | WING BODY TO VAPOR BARRIER-LEFT | | | | | | | | | | | | | |
| 0001 | 20 | GA | | 26-11 | 33-43-11 | D40302P | 2 | | D41392P | 8 | | | | ALL | |
| 0005 | 20 | GA | | 26-11 | 33-44-21 | D40302P | 5 | | D41392P | 10 | | | | ALL | |
| 0012 | 12 | GA | | 2-4 | 33-42-11 | D02306 | 2 | | GD00583 | ST.. | E | | | ALL | |
| 1001 | 12 | HE | AF | 2-11 | 33-42-11 | D02306 | 3 | | L00356 | =P | M | | | ALL | |
| 1001Z | | | AF | 0-0 | 33-42-11 | GD02678 | ST.. | E | GD00583 | ST.. | E | * | | ALL | |
| 1002 | 12 | HE | AG | 2-5 | 33-42-11 | D02306 | 8 | | GD00582 | AC.. | E | * | | ALL | |
| 1002Z | | | AG | 0-0 | 33-42-11 | GD02678 | ST.. | E | GD00582 | AC.. | E | * | | ALL | |
| 1003 | 12 | HE | AH | 1-8 | 33-42-11 | L00356 | =G | M | GD00582 | AC.. | E | * | | ALL | |
| 1003Z | | | AH | 0-0 | 33-42-11 | GD00583 | ST.. | E | GD00582 | AC.. | E | * | | ALL | |
| 1004 | 20 | GE | AI | 20-0 | 27-81-31 | D40302P | 12 | | SP02194 | | 9 | | | ALL | |
| 1004Z | | | AI | 0-0 | 27-81-31 | D40302P | S/R | | GD04200 | DC.. | E | * | | ALL | |
| 1005 | 20 | GE | AJ | 26-2 | 27-81-31 | D41392P | 11 | | SP02194 | | 9 | | | ALL | |
| 1005Z | | | AJ | 0-0 | 27-81-31 | D41392P | S/R | | GD04200 | DC.. | E | * | | ALL | |
| 2001B | 20 | GB | AD | 26-11 | 27-51-41 | D40302P | 13 | | D41392P | 3 | | | | ALL | |
| 2001R | 20 | GB | AD | 0-0 | 27-51-41 | D40302P | 14 | | D41392P | 2 | | | | ALL | |
| 2501B | 20 | GF | AE | 10-4 | 33-42-11 | D40302P | 3 | | D02306 | 5 | | | | ALL | |
| 2501R | 20 | GF | AE | 0-0 | 33-42-11 | D40302P | 4 | | D02306 | 7 | | | | ALL | |
| 2501Z | | | AE | 0-0 | 33-42-11 | D40302P | S/R | | GD02678 | ST.. | E | * | | ALL | |
| 4001B | 20 | GD | AB | 26-11 | 27-51-41 | D40302P | 18 | | D41392P | 5 | | | | ALL | |
| 4001G | 20 | GD | AB | 0-0 | 27-51-41 | D40302P | 19 | | D41392P | 7 | | | | ALL | |
| 4001R | 20 | GD | AB | 0-0 | 27-51-41 | D40302P | 20 | | D41392P | 4 | | | | ALL | |
| 4001Y | 20 | GD | AB | 0-0 | 27-51-41 | D40302P | 21 | | D41392P | 6 | | | | ALL | |
| A-B | | | | 0-0 | 27-81-31 | S10589 | 3 | | SP02194 | CAP | Y | | | ALL | |
| A-C | | | | 0-0 | 27-81-31 | S10589 | 1 | | GD04200 | DC.. | E | | | ALL | |
| A-D | | | | 0-0 | 27-81-31 | S10589 | 2 | | SP02194 | | 9 | | | ALL | |
| YAAA | | | | 0-0 | 33-43-11 | D40302P | S/R | | GD03019 | ST.. | E | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W3340

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3348 | 286N3348 | | | WING TIP POSITION LIGHTS-LEFT | | | | | | | | | | | |
| 0001 | 12 | | GA | | 2-0 | 33-43-11 | D07084 | | 5 | | GD01228 | ST.. | E | | ALL |
| 0005 | 12 | | GA | | 2-0 | 33-43-11 | D07084 | | 7 | | SM00002 | | | 9 | ALL |
| 2001B | 12 | | GB | AA | 4-0 | 33-43-11 | D00022 | | 1 | | SM00002 | | | 9 | ALL |
| 2001R | 12 | | GB | AA | 0-0 | 33-43-11 | D00022 | | 2 | | SP01872 | | | 9 | ALL |
| 2002B | 12 | | GB | AB | 4-0 | 33-43-11 | D00022 | | 3 | | SM00004 | | | 9 | ALL |
| 2002R | 12 | | GB | AB | 0-0 | 33-43-11 | D00022 | | 4 | | SM00006 | | | 9 | ALL |
| 2003B | 12 | | GB | AC | 7-0 | 33-43-11 | D00036 | | 1 | | SM00002 | | | 9 | ALL |
| 2003R | 12 | | GB | AC | 0-0 | 33-43-11 | D00036 | | 2 | | SP01872 | | | 9 | ALL |
| 2004B | 12 | | GB | AD | 7-0 | 33-43-11 | D00036 | | 3 | | SM00004 | | | 9 | ALL |
| 2004R | 12 | | GB | AD | 0-0 | 33-43-11 | D00036 | | 4 | | SM00006 | | | 9 | ALL |
| 2005B | 12 | | GB | AF | 2-0 | 33-43-11 | D07084 | | 4 | | SP01874 | | | 9 | ALL |
| 2005R | 12 | | GB | AF | 0-0 | 33-43-11 | D07084 | | 1 | | SP01872 | | | 9 | ALL |
| 2006B | 12 | | GB | AG | 2-0 | 33-43-11 | D07084 | | 8 | | SM00004 | | | 9 | ALL |
| 2006R | 12 | | GB | AG | 0-0 | 33-43-11 | D07084 | | 3 | | SM00006 | | | 9 | ALL |

WIRE LIST

D280N032

91-21-11

Section W3340

Page 3 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|-----|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3366 | 286N3366 | | | | LWR L. STRUT TO BLEED AIR VALVE | | | | | | | | | | | | |
| 0001 | 18 | | 7A | | 3-4 | 26-11-12 | D40816P | | 5 | | | D02122 | | A | | ALL | |
| 0002 | 18 | | 7A | | 3-4 | 26-11-12 | D40816P | | 2 | | | D02122 | | D | | ALL | |
| 0003 | 20 | | 7A | | 2-5 | 36-11-12 | D40816P | | 3 | | | D02780 | | 6 | | ALL | |
| 0004 | 18 | | 7A | | 3-0 | 36-11-12 | D02780 | | 5 | | | GD01556 | DC.. | N | | ALL | |
| 0005 | 20 | | 7A | | 2-5 | 36-11-12 | D40816P | | 4 | | | D02780 | | 3 | | ALL | |
| 0006 | 18 | | 7A | | 3-0 | 36-11-12 | D02780 | | 10 | | | GD01556 | DC.. | N | | ALL | |
| 0007 | 20 | | 7A | | 2-5 | 36-11-12 | D40816P | | 1 | | | D02780 | | 1 | | ALL | |
| 0008 | 20 | | 7A | | 2-5 | 36-11-12 | D40816P | | 6 | | | D02780 | | 8 | | ALL | |
| 0009 | 18 | | 7A | | 3-0 | 36-11-12 | D02780 | | 9 | | | GD01556 | DC.. | N | | ALL | |
| W3368 | 286N3368 | | | | LEFT FIREWALL DISC. TO NACELLE OVHT DETECTORS | | | | | | | | | | | | |
| 0001 | 18 | | 7A | | 2-10 | 26-11-12 | D41072P | | 5 | | | D02402 | | A | | ALL | |
| 0002 | 18 | | 7A | | 2-10 | 26-11-12 | D41072P | | 2 | | | D02402 | | D | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W3360

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3370 | 286N3370 | | | | | LEFT STRUT DISC TO STRUT OVHT SWITCHES | | | | | | | | | |
| 0001 | 20 | | 7A | | 6-3 | 26-11-12 | D41162J | | 5 | | D41072J | | 5 | | ALL |
| 0002 | 20 | | 7A | | 6-3 | 26-11-12 | D41162J | | 2 | | D41072J | | 2 | | ALL |
| 0003 | 18 | | 7A | | 3-2 | 26-12-11 | D41162J | | 3 | | S10199 | =1 | L | * | ALL |
| 0004 | 18 | | 7A | | 3-2 | 26-12-11 | D41162J | | 4 | | S10199 | =1 | L | * | ALL |
| 0005 | 18 | | 7A | | 2-6 | 26-12-11 | S10199 | | =2 | L | GD02035 | DC.. | N | | ALL |

WIRE LIST
D280N032

91-21-11
Section W3370
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|---|---------|----------|---------|-------|------|------|---------|-------|------|-------------|---------|--------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W3380 | 286N3380 | | | LEFT ENGINE STRUT TO LEFT FRONT/SPAR DISC | | | | | | | | | | | | |
| 0012 | 20 | GA | | | 20-8 | SPARE | D42278J | 16 | | | D41354P | 16 | | | ALL | |
| 0018R | 20 | QA | | | 20-8 | 26-11-11 | D42278J | 25 | | | D41354P | 25 | | | ALL | |
| 0019R | 20 | QA | | | 20-8 | 26-11-11 | D42278J | 33 | | | D41354P | 33 | | | ALL | |
| 0020R | 20 | QA | | | 20-8 | 26-11-11 | D42278J | 27 | | | D41354P | 27 | | | ALL | |
| 0021 | 18 | GA | | | 20-8 | 26-13-11 | D42278J | 28 | | | D41354P | 28 | 18 | | ALL | |
| 0022 | 18 | GA | | | 20-8 | 26-13-11 | D42278J | 34 | | | D41354P | 34 | 18 | | ALL | |
| 0026 | 20 | GA | | | 20-8 | 78-34-11 | D41354P | 32 | | | D42278J | 26 | | | ALL | |
| 1001 | 20 | GE | T | | 20-8 | 74-31-11 | D42278J | 15 | | | D41354P | 15 | | | ALL | |
| 1001Z | | | T | | 0-0 | 74-31-11 | D42278J | S/R | | | D41354P | S/R | | | ALL | |
| 2501B | 20 | GF | AA | | 20-8 | 77-12-11 | D42278J | 5 | | | D41354P | 5 | | | ALL | |
| 2501R | 20 | GF | AA | | 0-0 | 77-12-11 | D42278J | 4 | | | D41354P | 4 | | | ALL | |
| 2501Z | | | AA | | 0-0 | 77-12-11 | D42278J | S/R | | | D41354P | S/R | | | ALL | |
| 2502B | 20 | GF | AB | | 20-8 | 77-12-21 | D42278J | 8 | | | D41354P | 8 | | | ALL | |
| 2502R | 20 | GF | AB | | 0-0 | 77-12-21 | D42278J | 7 | | | D41354P | 7 | | | ALL | |
| 2502Z | | | AB | | 0-0 | 77-12-21 | D42278J | S/R | | | D41354P | S/R | | | ALL | |
| 2503B | 20 | GF | AF | | 20-8 | 74-31-11 | D42278J | 2 | | | D41354P | 2 | | | ALL | |
| 2503R | 20 | GF | AF | | 0-0 | 74-31-11 | D42278J | 3 | | | D41354P | 3 | | | ALL | |
| 2503Z | | | AF | | 0-0 | 74-31-11 | D42278J | S/R | | | D41354P | S/R | | | ALL | |
| 2504B | 20 | GF | AG | | 20-8 | SPARE | D42278J | 17 | | | D41354P | 17 | | | ALL | |
| 2504R | 20 | GF | AG | | 0-0 | SPARE | D42278J | 18 | | | D41354P | 18 | | | ALL | |
| 2504Z | | | AG | | 0-0 | SPARE | D42278J | S/R | | | D41354P | S/R | | | ALL | |
| 2505B | 20 | GF | AH | | 20-8 | SPARE | D42278J | 30 | | | D41354P | 30 | | | ALL | |
| 2505R | 20 | GF | AH | | 0-0 | SPARE | D42278J | 31 | | | D41354P | 31 | | | ALL | |
| 2505Z | | | AH | | 0-0 | SPARE | D42278J | S/R | | | D41354P | S/R | | | ALL | |
| 2506B | 18 | GF | AJ | | 20-8 | 30-34-21 | D42278J | 35 | | | D41354P | 37 | 18 | | 001-099 | |
| 2506B | 18 | GF | AK | | 20-8 | 30-34-21 | D42278J | 35 | | | D41354P | 37 | 18 | | 115-199 | |
| 2506R | 18 | GF | AJ | | 0-0 | 30-34-21 | D42278J | 36 | | | D41354P | 38 | 18 | | 001-099 | |
| 2506R | 18 | GF | AK | | 0-0 | 30-34-21 | D42278J | 36 | | | D41354P | 38 | 18 | | 115-199 | |
| 2506Z | | | AJ | | 0-0 | 30-34-21 | D42278J | S/R | | | D41354P | S/R | | | 001-099 | |
| 2506Z | | | AK | | 0-0 | 30-34-21 | D42278J | S/R | | | D41354P | S/R | | | 115-199 | |
| 3501B | 20 | GG | AE | | 20-8 | 80-11-11 | D42278J | 12 | | | D41354P | 12 | | | ALL | |
| 3501R | 20 | GG | AE | | 0-0 | 80-11-11 | D42278J | 13 | | | D41354P | 13 | | | ALL | |
| 3501Y | 20 | GG | AE | | 0-0 | 80-11-11 | D42278J | 14 | | | D41354P | 14 | | | ALL | |
| 3501Z | | | AE | | 0-0 | 80-11-11 | D42278J | S/R | | | D41354P | S/R | | | ALL | |
| 4251B | 20 | GH | AD | | 20-8 | 79-35-11 | D42278J | 11 | | | D41354P | 11 | | | ALL | |
| 4251G | 20 | GH | AD | | 0-0 | 79-33-11 | D42278J | 10 | | | D41354P | 10 | | | ALL | |
| 4251R | 20 | GH | AD | | 0-0 | 73-33-11 | D42278J | 1 | | | D41354P | 1 | | | ALL | |
| 4251Y | 20 | GH | AD | | 0-0 | 73-34-11 | D42278J | 21 | | | D41354P | 21 | | | ALL | |
| 4251Z | | | AD | | 0-0 | 79-35-11 | D42278J | S/R | | | D41354P | S/R | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W3380

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3380 | 286N3380 | | | LEFT ENGINE STRUT TO LEFT FRONT/SPAR DISC (continued) | | | | | | | | | | | |
| 4501G | 20 | DU | AC | | 20-8 | 77-21-11 | D42278J | 22 | 4H | | D41354P | 22 | TC | | ALL |
| 4501W | 20 | DU | AC | | 0-0 | 77-21-11 | D42278J | 23 | 4L | | D41354P | 23 | TD | | ALL |
| 4501Z | | | AC | | 0-0 | 77-21-11 | D42278J | S/R | | | D41354P | S/R | | | ALL |
| YAAA | | | | | 0-0 | 80-11-11 | D41354P | S/R | | | GD03015 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3380

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3400 | | 286N3400 | | | | RIGHT ENGINE STRUT TO RIGHT FRONT SPAR DISC | | | | | | | | | |
| 0035 | 20 | GA | | | 13-5 | 28-42-11 | D40004P | 30 | | | D01830 | 3 | | | ALL |
| 0036 | 18 | GA | | | 1-9 | 28-42-11 | D01830 | 2 | 18 | | GD00188 | DC.. | E | | ALL |
| 0037 | 18 | GA | | | 1-10 | 28-42-11 | D01830 | 4 | 18 | | GD00189 | ST.. | E | | ALL |
| 0038 | 18 | GA | | | 20-10 | 26-18-21 | D40016P | 2 | | | D42292P | 26 | | | ALL |
| 0040R | 20 | QA | | | 20-10 | 26-11-21 | D40016P | 4 | | | D42294P | 4 | | | ALL |
| 0041R | 20 | QA | | | 20-10 | 26-11-21 | D40016P | 20 | | | D42294P | 19 | | | ALL |
| 0042R | 20 | QA | | | 20-10 | 26-11-21 | D40016P | 6 | | | D42294P | 6 | | | ALL |
| 0043 | 20 | GA | | | 20-10 | 29-11-21 | D40016P | 10 | | | D42292P | 4 | | | ALL |
| 0044 | 20 | GA | | | 20-10 | 29-11-21 | D40016P | 11 | | | D42292P | 5 | | | ALL |
| 0047 | 20 | GA | | | 20-10 | 29-11-21 | D40016P | 7 | | | D42294P | 7 | | | ALL |
| 0052 | 18 | GA | | | 20-10 | 26-13-21 | D40016P | 8 | | | D42294P | 8 | | | ALL |
| 0053 | 18 | GA | | | 20-10 | 26-13-21 | D40016P | 12 | | | D42294P | 12 | | | ALL |
| 0062 | 20 | GA | | | 20-10 | SPARE | D40004P | 25 | | | D42292P | 6 | | | ALL |
| 0064 | 20 | GA | | | 20-10 | SPARE | D40004P | 41 | | | D42292P | 7 | | | ALL |
| 0067 | 20 | GA | | | 20-10 | SPARE | D40016P | 27 | | | D42294P | 5 | | | 001-099 |
| 0068 | 20 | GA | | | 20-10 | 29-11-22 | D40004P | 42 | | | D42292P | 8 | | | ALL |
| 0073 | 20 | GA | | | 20-10 | 29-11-22 | D42292P | 9 | | | D40004P | 14 | | | ALL |
| 0083 | 20 | GA | | | 20-10 | 29-11-22 | D42292P | 12 | | | D40004P | 8 | | | ALL |
| 0092 | 20 | GA | | | 26-6 | 30-11-11 | D00570 | 4 | | | D40004P | 52 | | | ALL |
| 0093 | 20 | GA | | | 26-6 | 30-11-11 | D00570 | 5 | | | D40004P | 53 | | | ALL |
| 0094 | 20 | GA | | | 26-6 | 30-11-11 | D00570 | 1 | | | D40004P | 54 | | | ALL |
| 0095 | 20 | GA | | | 1-9 | 30-11-11 | D00570 | 2 | | | GD00238 | DC.. | E | | ALL |
| 0096 | 20 | GA | | | 1-9 | 30-11-11 | D00570 | 3 | | | GD00238 | DC.. | E | | ALL |
| 0097 | 18 | GA | | | 1-9 | 30-11-11 | D00570 | 6 | | | GD00239 | ST.. | E | | ALL |
| 1001 | 18 | GE | AR | | 20-10 | 73-21-21 | D42294P | 9 | | | D40016P | 5 | | | 001-099 |
| 1001Z | | | AR | | 0-0 | 73-21-21 | D42294P | S/R | | | D40016P | S/R | | | 001-099 |
| 1002 | 20 | GE | AU | | 20-10 | 76-11-12 | D40016P | 1 | | | SM00001 | 9 | | | 001-099 |
| 1002 | 20 | GE | AN | | 20-10 | 76-11-12 | D40016P | 1 | | | SM00001 | 9 | | | 115-199 |
| 1002Z | | | AU | | 0-0 | 76-11-12 | D40016P | S/R | | | SM00REF | 1 | | AA | 001-099 |
| 1002Z | | | AN | | 0-0 | 76-11-12 | D40016P | S/R | | | SM00REF | 0001 | | AC | 115-199 |
| 1003 | 20 | GE | AS | | 0-12 | 76-11-12 | D42292P | 19 | | | SM00001 | 9 | | | 001-099 |
| 1003 | 20 | GE | AK | | 20-10 | 76-11-12 | D40004P | 27 | | | SM00001 | 9 | | | 115-199 |
| 1003Z | | | AS | | 0-0 | 76-11-12 | D42292P | S/R | | | SM00REF | 1 | | AA | 001-099 |
| 1003Z | | | AK | | 0-0 | 76-11-12 | D40004P | S/R | | | SM00REF | 0001 | | AC | 115-199 |
| 1004 | 20 | GE | AT | | 20-10 | 76-11-12 | D40004P | 27 | | | SM00001 | 9 | | | 001-099 |
| 1004 | 20 | GE | AM | | 0-12 | 76-11-12 | D42292P | 19 | | | SM00001 | 9 | | | 115-199 |
| 1004Z | | | AT | | 0-0 | 76-11-12 | D40004P | S/R | | | SM00REF | 1 | | AA | 001-099 |
| 1004Z | | | AM | | 0-0 | 76-11-12 | D42292P | S/R | | | SM00REF | 0001 | | AC | 115-199 |
| 1005 | 20 | GE | AB | | 20-10 | SPARE | D40004P | 18 | | | D42292P | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3400 | 286N3400 | | | RIGHT ENGINE STRUT TO RIGHT FRONT SPAR DISC (continued) | | | | | | | | | | | |
| 1005Z | | | | AB | 0-0 | SPARE | D40004P | | S/R | | D42292P | | S/R | | 001-099 |
| 1006 | 18 | GE | T | | 20-10 | 73-21-21 | D42294P | | 9 | | D40016P | | 5 | | 115-199 |
| 1006Z | | | | T | 0-0 | 73-21-21 | D42294P | | S/R | | D40016P | | S/R | | 115-199 |
| 1007 | 18 | GE | AW | | 20-10 | 28-22-21 | D40016P | | 15 | | D42292P | | 11 | | 001-099 |
| 1007 | 18 | GE | AP | | 20-10 | 28-22-21 | D40016P | | 15 | | D42292P | | 11 | | 115-199 |
| 1007Z | | | | AW | 0-0 | 28-22-21 | D40016P | | S/R | | D42292P | | S/R | | 001-099 |
| 1007Z | | | | AP | 0-0 | 28-22-21 | D40016P | | S/R | | D42292P | | S/R | | 115-199 |
| 1009 | 18 | HP | AZ | | 3-10 | 26-18-21 | D40016P | | 3 | | D01992 | | = 1 | | 001-099 |
| 1009 | 18 | HP | AR | | 3-10 | 26-18-21 | D40016P | | 3 | | D01992 | | = 1 | | 115-199 |
| 1009Z | | | | AZ | 0-0 | 26-18-21 | D40016P | | S/R | | GD02707 | | ST.. | E | 001-099 |
| 1009Z | | | | AR | 0-0 | 26-18-21 | D40016P | | S/R | | GD02707 | | ST.. | E | 115-199 |
| 2501B | 20 | GF | BE | | 20-10 | 73-21-21 | D42292P | | 14 | | D40004P | | 46 | | 001-099 |
| 2501B | 20 | GF | AA | | 20-10 | 73-21-21 | D42292P | | 14 | | D40004P | | 46 | | 115-199 |
| 2501R | 20 | GF | BE | | 0-0 | 73-21-21 | D42292P | | 13 | | D40004P | | 45 | | 001-099 |
| 2501R | 20 | GF | AA | | 0-0 | 73-21-21 | D42292P | | 13 | | D40004P | | 45 | | 115-199 |
| 2501Z | | | | BE | 0-0 | 73-21-21 | D42292P | | | AD | D40004P | | | AB | 001-099 |
| 2501Z | | | | AA | 0-0 | 73-21-21 | D42292P | | | AA | D40004P | | | AB | 115-199 |
| 2502B | 20 | GF | BD | | 20-10 | 73-21-21 | D42292P | | 28 | | D40004P | | 48 | | 001-099 |
| 2502B | 20 | GF | AB | | 20-10 | 73-21-21 | D42292P | | 28 | | D40004P | | 48 | | 115-199 |
| 2502R | 20 | GF | BD | | 0-0 | 73-21-21 | D42292P | | 29 | | D40004P | | 47 | | 001-099 |
| 2502R | 20 | GF | AB | | 0-0 | 73-21-21 | D42292P | | 29 | | D40004P | | 47 | | 115-199 |
| 2502Z | | | | BD | 0-0 | 73-21-21 | D42292P | | | AD | D40004P | | | AB | 001-099 |
| 2502Z | | | | AB | 0-0 | 73-21-21 | D42292P | | | AA | D40004P | | | AB | 115-199 |
| 2503B | 20 | GF | BF | | 20-10 | 73-21-21 | D42292P | | 15 | | D40004P | | 50 | | 001-099 |
| 2503B | 20 | GF | AC | | 20-10 | 73-21-21 | D42292P | | 15 | | D40004P | | 50 | | 115-199 |
| 2503R | 20 | GF | BF | | 0-0 | 73-21-21 | D42292P | | 30 | | D40004P | | 49 | | 001-099 |
| 2503R | 20 | GF | AC | | 0-0 | 73-21-21 | D42292P | | 30 | | D40004P | | 49 | | 115-199 |
| 2503Z | | | | BF | 0-0 | 73-21-21 | D42292P | | | AD | D40004P | | | AB | 001-099 |
| 2503Z | | | | AC | 0-0 | 73-21-21 | D42292P | | | AA | D40004P | | | AB | 115-199 |
| 2504B | 16 | GF | BB | | 20-10 | 75-31-11 | D40016P | | 9 | | D42294P | | 11 | | 001-099 |
| 2504B | 16 | GF | AG | | 20-10 | 75-31-11 | D42294P | | 11 | | D40016P | | 9 | | 115-199 |
| 2504R | 16 | GF | BB | | 0-0 | 75-31-11 | D40016P | | 17 | | D42294P | | 17 | | 001-099 |
| 2504R | 16 | GF | AG | | 0-0 | 75-31-11 | D42294P | | 17 | | D40016P | | 17 | | 115-199 |
| 2504Z | | | | BB | 0-0 | 75-31-11 | D40016P | | S/R | | D42294P | | S/R | | 001-099 |
| 2504Z | | | | AG | 0-0 | 75-31-11 | D42294P | | S/R | | D40016P | | S/R | | 115-199 |
| 2505B | 20 | GF | AH | | 20-10 | SPARE | D40016P | | 28 | | D42294P | | 1 | | 115-199 |
| 2505R | 20 | GF | AH | | 0-0 | SPARE | D40016P | | 29 | | D42294P | | 2 | | 115-199 |
| 2505Z | | | | AH | 0-0 | SPARE | D40016P | | S/R | | D42294P | | S/R | | 115-199 |
| 2506B | 20 | GF | AJ | | 20-10 | SPARE | D40016P | | 30 | | D42294P | | 3 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | | | | | |
|--------------|-----------------|--|-------|---------|----------|---------|------|--------|---------|---------|------|--------|-------------|--|--|--|--|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | | | |
| W3400 | 286N3400 | RIGHT ENGINE STRUT TO RIGHT FRONT SPAR DISC (continued) | | | | | | | | | | | | | | | | | |
| 2506R | 20 | GF | AJ | 0-0 | SPARE | D40016P | 27 | | D42294P | 5 | | | 115-199 | | | | | | |
| 2506Z | | | AJ | 0-0 | SPARE | D40016P | S/R | | D42294P | S/R | | | 115-199 | | | | | | |
| 2509B | 20 | GF | AC | 20-10 | SPARE | D40004P | 38 | | D42292P | 38 | | | 001-099 | | | | | | |
| 2509R | 20 | GF | AC | 0-0 | SPARE | D40004P | 39 | | D42292P | 39 | | | 001-099 | | | | | | |
| 2509Z | | | AC | 0-0 | SPARE | D40004P | S/R | | D42292P | S/R | | | 001-099 | | | | | | |
| 2510B | 20 | GF | BG | 20-10 | SPARE | D42292P | 40 | | D40004P | 12 | | | 001-099 | | | | | | |
| 2510R | 20 | GF | BG | 0-0 | SPARE | D42292P | 41 | | D40004P | 13 | | | 001-099 | | | | | | |
| 2510Z | | | BG | 0-0 | SPARE | D42292P | S/R | | D40004P | S/R | | | 001-099 | | | | | | |
| 3503B | 20 | GG | AQ | 20-10 | 76-11-12 | D40004P | 26 | | D42292P | 1 | | | 001-099 | | | | | | |
| 3503B | 20 | GG | AF | 20-10 | 76-11-12 | D40004P | 26 | | D42292P | 1 | | | 115-199 | | | | | | |
| 3503R | 20 | GG | AQ | 0-0 | 76-11-12 | D40004P | 28 | | D42292P | 2 | | | 001-099 | | | | | | |
| 3503R | 20 | GG | AF | 0-0 | 76-11-12 | D40004P | 28 | | D42292P | 2 | | | 115-199 | | | | | | |
| 3503Y | 20 | GG | AQ | 0-0 | 76-11-12 | D40004P | 29 | | D42292P | 3 | | | 001-099 | | | | | | |
| 3503Y | 20 | GG | AF | 0-0 | 76-11-12 | D40004P | 29 | | D42292P | 3 | | | 115-199 | | | | | | |
| 3503Z | | | AQ | 0-0 | 76-11-12 | D40004P | S/R | | D42292P | S/R | | | 001-099 | | | | | | |
| 3503Z | | | AF | 0-0 | 76-11-12 | D40004P | S/R | | D42292P | S/R | | | 115-199 | | | | | | |
| 3504B | 20 | GG | AA | 20-10 | SPARE | D40016P | 28 | | D42294P | 1 | | | 001-099 | | | | | | |
| 3504R | 20 | GG | AA | 0-0 | SPARE | D40016P | 29 | | D42294P | 2 | | | 001-099 | | | | | | |
| 3504Y | 20 | GG | AA | 0-0 | SPARE | D40016P | 30 | | D42294P | 3 | | | 001-099 | | | | | | |
| 3504Z | | | AA | 0-0 | SPARE | D40016P | S/R | | D42294P | S/R | | | 001-099 | | | | | | |
| 4501G | 20 | DU | BA | 20-10 | 75-31-11 | D40004P | 34 | TC | D42292P | 17 | 4H | | 001-099 | | | | | | |
| 4501G | 20 | DU | AD | 20-10 | 75-31-11 | D42292P | 17 | 4H | D40004P | 34 | TC | | 115-199 | | | | | | |
| 4501W | 20 | DU | BA | 0-0 | 75-31-11 | D40004P | 33 | TD | D42292P | 16 | 4L | | 001-099 | | | | | | |
| 4501W | 20 | DU | AD | 0-0 | 75-31-11 | D42292P | 16 | 4L | D40004P | 33 | TD | | 115-199 | | | | | | |
| 4501Z | | | BA | 0-0 | 75-31-11 | D40004P | S/R | | D42292P | S/R | | | 001-099 | | | | | | |
| 4501Z | | | AD | 0-0 | 75-31-11 | D42292P | S/R | | D40004P | S/R | | | 115-199 | | | | | | |
| 4502G | 20 | DU | BC | 20-10 | 77-21-11 | D40004P | 16 | TC | D42292P | 33 | 4H | | 001-099 | | | | | | |
| 4502G | 20 | DU | AE | 20-10 | 77-21-11 | D42292P | 33 | 4H | D40004P | 16 | TC | | 115-199 | | | | | | |
| 4502W | 20 | DU | BC | 0-0 | 77-21-11 | D40004P | 15 | TD | D42292P | 34 | 4L | | 001-099 | | | | | | |
| 4502W | 20 | DU | AE | 0-0 | 77-21-11 | D42292P | 34 | 4L | D40004P | 15 | TD | | 115-199 | | | | | | |
| 4502Z | | | BC | 0-0 | 77-21-11 | D40004P | S/R | | D42292P | S/R | | | 001-099 | | | | | | |
| 4502Z | | | AE | 0-0 | 77-21-11 | D42292P | S/R | | D40004P | S/R | | | 115-199 | | | | | | |
| FRAA | | | | 0-0 | 73-21-21 | D42292P | | | AA | D42292P | 31 | | 115-199 | | | | | | |
| FRAB | | | | 0-0 | 73-21-21 | D40004P | | | AB | D40004P | 51 | | ALL | | | | | | |
| FRAD | | | | 0-0 | 73-21-21 | D42292P | | | AD | D42292P | 31 | | 001-099 | | | | | | |
| YAAA | | | | 0-0 | 76-11-12 | GD03092 | ST.. | E | * | D40004P | S/R | | ALL | | | | | | |
| YAAB | | | | 0-0 | 26-18-21 | GD03092 | ST.. | E | * | D40016P | S/R | | ALL | | | | | | |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3401 | 286N3401 | | | R. WHEEL WELL/SPOILER DISC. PNL TO SPOILER #12-CHANNEL L2A | | | | | | | | | | | |
| 0001 | 20 | | GA | | 1-0 | 27-61-13 | D00663 | | 10 | | GD00576 | ST.. | E | | ALL |
| 4501RB | 20 | | 7N | AA | 46-0 | 27-61-13 | D40575J | | 7 | | D00663 | 7 | | | 001-099 |
| 4501RB | 20 | | 7N | AA | 45-0 | 27-61-13 | D40575J | | 7 | | D00663 | 7 | | | 115-199 |
| 4501WB | 20 | | 7N | AA | 0-0 | 27-61-13 | D40575J | | 3 | | D00663 | 1 | | | ALL |
| 4501WK | 20 | | 7N | AA | 0-0 | 27-61-13 | D40575J | | 8 | | D00663 | 8 | | | ALL |
| 4501WN | 20 | | 7N | AA | 0-0 | 27-61-13 | D40575J | | 6 | | D00663 | 6 | | | ALL |
| 4501WO | 20 | | 7N | AA | 0-0 | 27-61-13 | D40575J | | 5 | | D00663 | 5 | | | ALL |
| 4501WR | 20 | | 7N | AA | 0-0 | 27-61-13 | D40575J | | 1 | | D00663 | 3 | | | ALL |
| 4501WV | 20 | | 7N | AA | 0-0 | 27-61-13 | D40575J | | 9 | | D00663 | 9 | | | ALL |
| 4501Z | | | | AA | 0-0 | 27-61-13 | D40575J | | S/R | | GD00576 | ST.. | E | | ALL |
| W3402 | 286N3402 | | | RIGHT ENGINE STRUT TO RIGHT FRONT/SPAR DISC | | | | | | | | | | | |
| 0004 | 18 | | GA | | 20-11 | 26-18-21 | D40032P | | 8 | | D42288J | 8 | | | ALL |
| 0006 | 18 | | GA | | 20-11 | 29-32-21 | D40032P | | 10 | | D42288J | 10 | | | ALL |
| 0017 | 20 | | GA | | 20-11 | 78-36-21 | D40032P | | 34 | | D42288J | 34 | | | ALL |
| 0018 | 20 | | GA | | 20-11 | 78-36-21 | D40032P | | 35 | | D42288J | 35 | | | ALL |
| 0020 | 20 | | GA | | 20-11 | 76-11-12 | D40032P | | 36 | | D42288J | 36 | | | ALL |
| 0021 | 20 | | GA | | 20-11 | 76-11-12 | D40032P | | 37 | | D42288J | 37 | | | ALL |
| 0035 | 20 | | GA | | 20-11 | SPARE | D40032P | | 1 | | D42288J | 1 | | | 115-199 |
| 0036 | 20 | | GA | | 20-11 | 78-36-21 | D40032P | | 33 | | D42288J | 33 | | | 003-099 |
| 1001 | 18 | | HP | AC | 2-10 | 26-18-21 | D40032P | | 9 | | D01988 | = 1 | | | ALL |
| 1001Z | | | | AC | 0-0 | 26-18-21 | D40032P | | S/R | | GD02707 | ST.. | E | | ALL |
| 1002 | 20 | | GE | T | 20-11 | 76-11-21 | D40032P | | 19 | | D42288J | 19 | | | ALL |
| 1002Z | | | | T | 0-0 | 76-11-21 | D40032P | | S/R | | D42288J | S/R | | | ALL |
| 2501B | 20 | | GF | AF | 20-11 | 79-34-11 | D40032P | | 31 | | D42288J | 31 | | | ALL |
| 2501R | 20 | | GF | AF | 0-0 | 79-34-11 | D40032P | | 32 | | D42288J | 32 | | | ALL |
| 2501Z | | | | AF | 0-0 | 79-34-11 | D40032P | | S/R | | D42288J | S/R | | | ALL |
| 2502B | 20 | | GF | AG | 20-11 | 79-34-11 | D40032P | | 6 | | D42288J | 6 | | | ALL |
| 2502R | 20 | | GF | AG | 0-0 | 79-34-11 | D40032P | | 5 | | D42288J | 5 | | | ALL |
| 2502Z | | | | AG | 0-0 | 79-34-11 | D40032P | | S/R | | D42288J | S/R | | | ALL |
| 2503B | 20 | | GF | AJ | 20-11 | 74-31-21 | D40032P | | 17 | | D42288J | 17 | | | ALL |
| 2503R | 20 | | GF | AJ | 0-0 | 74-31-21 | D40032P | | 18 | | D42288J | 18 | | | ALL |
| 2503Z | | | | AJ | 0-0 | 74-31-21 | D40032P | | S/R | | D42288J | S/R | | | ALL |
| 2504B | 20 | | GF | AA | 20-11 | SPARE | D40032P | | 1 | | D42288J | 1 | | | 001-099 |
| 2504R | 20 | | GF | AA | 0-0 | SPARE | D40032P | | 2 | | D42288J | 2 | | | 001-099 |
| 2504Z | | | | AA | 0-0 | SPARE | D40032P | | 4 | | D42288J | 4 | | | 001-099 |
| 2505B | 20 | | GF | AM | 20-11 | SPARE | D40032P | | 2 | | D42288J | 2 | | | 115-199 |
| 2505R | 20 | | GF | AM | 0-0 | SPARE | D40032P | | 3 | | D42288J | 3 | | | 115-199 |
| 2505Z | | | | AM | 0-0 | SPARE | D40032P | | 4 | | D42288J | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|---------|------|-------------|--------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W3402 | 286N3402 | | | | RIGHT ENGINE STRUT TO RIGHT FRONT/SPAR DISC (continued) | | | | | | | | | | | |
| 3502B | 20 | GG | AH | | 20-11 | 30-21-11 | | D40032P | 11 | | | D42288J | 11 | | | ALL |
| 3502R | 20 | GG | AH | | 0-0 | 30-21-11 | | D40032P | 12 | | | D42288J | 12 | | | ALL |
| 3502Y | 20 | GG | AH | | 0-0 | 30-21-11 | | D40032P | 13 | | | D42288J | 13 | | | ALL |
| 3502Z | | | AH | | 0-0 | 30-21-11 | | D40032P | S/R | | | D42288J | S/R | | | ALL |
| 3503B | 20 | GG | AB | | 20-11 | 73-31-11 | | D40032P | 15 | | | D42288J | 15 | | | ALL |
| 3503R | 20 | GG | AB | | 0-0 | 73-31-11 | | D40032P | 14 | | | D42288J | 14 | | | ALL |
| 3503Y | 20 | GG | AB | | 0-0 | 73-31-11 | | D40032P | 16 | | | D42288J | 16 | | | ALL |
| 3503Z | | | AB | | 0-0 | 73-31-11 | | D40032P | S/R | | | D42288J | S/R | | | ALL |
| 3504B | 20 | GG | AD | | 20-11 | 79-31-11 | | D40032P | 26 | | | D42288J | 26 | | | ALL |
| 3504R | 20 | GG | AD | | 0-0 | 79-31-11 | | D40032P | 27 | | | D42288J | 27 | | | ALL |
| 3504Y | 20 | GG | AD | | 0-0 | 79-31-11 | | D40032P | 25 | | | D42288J | 25 | | | ALL |
| 3504Z | | | AD | | 0-0 | 79-31-11 | | D40032P | S/R | | | D42288J | S/R | | | ALL |
| 3505B | 20 | GG | AE | | 20-11 | 79-32-11 | | D40032P | 28 | | | D42288J | 28 | | | ALL |
| 3505R | 20 | GG | AE | | 0-0 | 79-32-11 | | D40032P | 29 | | | D42288J | 29 | | | ALL |
| 3505Y | 20 | GG | AE | | 0-0 | 79-32-11 | | D40032P | 30 | | | D42288J | 30 | | | ALL |
| 3505Z | | | AE | | 0-0 | 79-32-11 | | D40032P | S/R | | | D42288J | S/R | | | ALL |
| 3506B | 20 | GG | AK | | 20-11 | SPARE | | D40032P | 40 | | | D42288J | 40 | | | ALL |
| 3506R | 20 | GG | AK | | 0-0 | SPARE | | D40032P | 41 | | | D42288J | 41 | | | ALL |
| 3506Y | 20 | GG | AK | | 0-0 | SPARE | | D40032P | 42 | | | D42288J | 42 | | | ALL |
| 3506Z | | | AK | | 0-0 | SPARE | | D40032P | S/R | | | D42288J | S/R | | | ALL |
| YAAA | | | | | 0-0 | 29-32-21 | | GD03088 | ST.. | E | | D40032P | S/R | | | 001-099 |
| YAAA | | | | | 0-0 | 29-32-21 | | GD03090 | ST.. | E | | D40032P | S/R | | | 115-199 |
| W3404 | 286N3404 | | | | RIGHT ENGINE STRUT TO RIGHT FRONT/SPAR DISC | | | | | | | | | | | |
| 0001 | 20 | GA | | | 0-8 | 77-31-11 | | D40020P | 26 | | | D40020P | 11 | | | ALL |
| 0002 | 20 | GA | | | 0-8 | 77-31-11 | | D40020P | 10 | | | D40020P | 9 | | | ALL |
| 0004 | 20 | GA | | | 0-8 | 77-31-11 | | D40020P | 22 | | | D40020P | 39 | | | ALL |
| 0005 | 20 | GA | | | 0-8 | 77-31-11 | | D42284P | 26 | | | D42284P | 11 | | | ALL |
| 0006 | 20 | GA | | | 0-8 | 77-31-11 | | D42284P | 10 | | | D42284P | 9 | | | ALL |
| 0007 | 20 | GA | | | 0-8 | 77-31-11 | | D42284P | 22 | | | D42284P | 39 | | | ALL |
| 0010 | 20 | GA | | | 20-6 | SPARE | | D40020P | 15 | | | D42284P | 15 | | | 115-199 |
| 1003 | 20 | GE | T | | 20-6 | 77-11-11 | | D40020P | 3 | | | D42284P | 3 | | | ALL |
| 1003Z | | | T | | 0-0 | 77-11-11 | | D40020P | S/R | | | D42284P | S/R | | | ALL |
| 2001B | 18 | GB | AE | | 20-6 | 22-33-11 | | D40020P | 14 | | | D42284P | 14 | | | ALL |
| 2001R | 18 | GB | AE | | 0-0 | 22-33-11 | | D40020P | 16 | | | D42284P | 16 | | | ALL |
| 2002B | 18 | GB | AF | | 20-6 | 22-33-11 | | D40020P | 35 | | | D42284P | 35 | | | ALL |
| 2002R | 18 | GB | AF | | 0-0 | 22-33-11 | | D40020P | 6 | | | D42284P | 6 | | | ALL |
| 2501B | 20 | GF | AD | | 20-6 | 77-12-31 | | D40020P | 30 | | | D42284P | 30 | | | ALL |
| 2501R | 20 | GF | AD | | 0-0 | 77-12-31 | | D40020P | 29 | | | D42284P | 29 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3404 | 286N3404 | | | | RIGHT ENGINE STRUT TO RIGHT FRONT/SPAR DISC (continued) | | | | | | | | | | | | |
| 2501Z | | | | AD | 0-0 | 77-12-31 | | D40020P | | S/R | | D42284P | | S/R | | ALL | |
| 2502B | 20 | GF | | AH | 20-6 | SPARE | | D40020P | | 21 | | D42284P | | 19 | | 001-099 | |
| 2502B | 20 | GF | | AN | 20-6 | SPARE | | D40020P | | 12 | | D42284P | | 12 | | 115-199 | |
| 2502R | 20 | GF | | AH | 0-0 | SPARE | | D40020P | | 27 | | D42284P | | 20 | | 001-099 | |
| 2502R | 20 | GF | | AN | 0-0 | SPARE | | D40020P | | 18 | | D42284P | | 18 | | 115-199 | |
| 2502Z | | | | AH | 0-0 | SPARE | | D40020P | | 28 | | D42284P | | S/R | | 001-099 | |
| 2502Z | | | | AN | 0-0 | SPARE | | D40020P | | S/R | | D42284P | | S/R | | 115-199 | |
| 2503B | 18 | GF | | AP | 20-6 | 73-21-22 | | D40020P | | 8 | | D42284P | | 8 | | 001-099 | |
| 2503B | 18 | GF | | AH | 20-6 | 73-21-22 | | D40020P | | 8 | | D42284P | | 8 | | 115-199 | |
| 2503R | 18 | GF | | AP | 0-0 | 73-21-22 | | D40020P | | 7 | | D42284P | | 7 | | 001-099 | |
| 2503R | 18 | GF | | AH | 0-0 | 73-21-22 | | D40020P | | 7 | | D42284P | | 7 | | 115-199 | |
| 2503Z | | | | AP | 0-0 | 73-21-22 | | D40020P | | S/R | | D42284P | | S/R | | 001-099 | |
| 2503Z | | | | AH | 0-0 | 73-21-22 | | D40020P | | S/R | | D42284P | | S/R | | 115-199 | |
| 2504B | 20 | GF | | AK | 20-6 | 75-31-11 | | D40020P | | 1 | | D42284P | | 1 | | 001-099 | |
| 2504B | 20 | GF | | AJ | 20-6 | 75-31-11 | | D40020P | | 1 | | D42284P | | 1 | | 115-199 | |
| 2504R | 20 | GF | | AK | 0-0 | 75-31-11 | | D40020P | | 13 | | D42284P | | 13 | | 001-099 | |
| 2504R | 20 | GF | | AJ | 0-0 | 75-31-11 | | D40020P | | 13 | | D42284P | | 13 | | 115-199 | |
| 2504Z | | | | AK | 0-0 | 75-31-11 | | D40020P | | S/R | | D42284P | | S/R | | 001-099 | |
| 2504Z | | | | AJ | 0-0 | 75-31-11 | | D40020P | | S/R | | D42284P | | S/R | | 115-199 | |
| 2505B | 16 | GF | | AJ | 20-6 | 75-31-11 | | D40020P | | 31 | | D42284P | | 31 | | 001-099 | |
| 2505B | 16 | GF | | AK | 20-6 | 75-31-11 | | D40020P | | 31 | | D42284P | | 31 | | 115-199 | |
| 2505R | 16 | GF | | AJ | 0-0 | 75-31-11 | | D40020P | | 33 | | D42284P | | 33 | | 001-099 | |
| 2505R | 16 | GF | | AK | 0-0 | 75-31-11 | | D40020P | | 33 | | D42284P | | 33 | | 115-199 | |
| 2505Z | | | | AJ | 0-0 | 75-31-11 | | D40020P | | S/R | | D42284P | | S/R | | 001-099 | |
| 2505Z | | | | AK | 0-0 | 75-31-11 | | D40020P | | S/R | | D42284P | | S/R | | 115-199 | |
| 2506B | 20 | GF | | AG | 20-6 | SPARE | | D40020P | | 15 | | D42284P | | 17 | | 001-099 | |
| 2506B | 18 | GF | | AM | 20-6 | 73-21-21 | | D40020P | | 2 | | D42284P | | 2 | | 115-199 | |
| 2506R | 20 | GF | | AG | 0-0 | SPARE | | D40020P | | 18 | | D42284P | | 18 | | 001-099 | |
| 2506R | 18 | GF | | AM | 0-0 | 73-21-21 | | D40020P | | 34 | | D42284P | | 34 | | 115-199 | |
| 2506Z | | | | AG | 0-0 | SPARE | | D40020P | | S/R | | D42284P | | S/R | | 001-099 | |
| 2506Z | | | | AM | 0-0 | 73-21-21 | | D40020P | | S/R | | D42284P | | S/R | | 115-199 | |
| 2507B | 18 | GF | | AR | 20-6 | 73-21-21 | | D40020P | | 2 | | D42284P | | 2 | | 001-099 | |
| 2507B | 20 | GF | | AP | 20-6 | SPARE | | D40020P | | 19 | | D42284P | | 19 | | 115-199 | |
| 2507R | 18 | GF | | AR | 0-0 | 73-21-21 | | D40020P | | 34 | | D42284P | | 34 | | 001-099 | |
| 2507R | 20 | GF | | AP | 0-0 | SPARE | | D40020P | | 20 | | D42284P | | 20 | | 115-199 | |
| 2507Z | | | | AR | 0-0 | 73-21-21 | | D40020P | | S/R | | D42284P | | S/R | | 001-099 | |
| 2507Z | | | | AP | 0-0 | SPARE | | D40020P | | S/R | | D42284P | | S/R | | 115-199 | |
| 4501R | 20 | RJ | | AB | 20-6 | 77-31-11 | | D40020P | | 40 | | D42284P | | 40 | | ALL | |
| 4501W | 20 | RJ | | AB | 0-0 | 77-31-11 | | D40020P | | 25 | | D42284P | | 25 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3404 | 286N3404 | | | RIGHT ENGINE STRUT TO RIGHT FRONT/SPAR DISC (continued) | | | | | | | | | | | |
| 4501Z | | | | AB | 0-0 | 77-31-11 | D40020P | 23 | | | D42284P | 23 | | | ALL |
| 4502R | 20 | RJ | | AC | 20-6 | 77-31-11 | D40020P | 42 | | | D42284P | 42 | | | ALL |
| 4502W | 20 | RJ | | AC | 0-0 | 77-31-11 | D40020P | 41 | | | D42284P | 41 | | | ALL |
| 4502Z | | | | AC | 0-0 | 77-31-11 | D40020P | 24 | | | D42284P | 24 | | | ALL |
| 5001B | 20 | GF | | AA | 20-6 | 77-11-11 | D40020P | 4 | | | D42284P | 4 | | | ALL |
| 5001R | 20 | GF | | AA | 0-0 | 77-11-11 | D40020P | 5 | | | D42284P | 5 | | | ALL |
| 5001Z | | | | AA | 0-0 | 77-11-11 | D40020P | S/R | | | D42284P | S/R | | | ALL |
| 5002B | 20 | GF | | AS | 20-6 | 77-11-11 | D40020P | 37 | | | D42284P | 37 | | | 001-099 |
| 5002B | 20 | GF | | AG | 20-6 | 77-11-11 | D40020P | 37 | | | D42284P | 37 | | | 115-199 |
| 5002R | 20 | GF | | AS | 0-0 | 77-11-11 | D40020P | 36 | | | D42284P | 36 | | | 001-099 |
| 5002R | 20 | GF | | AG | 0-0 | 77-11-11 | D40020P | 36 | | | D42284P | 36 | | | 115-199 |
| 5002Z | | | | AS | 0-0 | 77-11-11 | D40020P | S/R | | | D42284P | S/R | | | 001-099 |
| 5002Z | | | | AG | 0-0 | 77-11-11 | D40020P | S/R | | | D42284P | S/R | | | 115-199 |
| YAAA | | | | | 0-0 | 77-11-11 | GD03110 | ST.. | E | | D40020P | S/R | | | ALL |
| W3405 | 286N3405 | | | R. WHEEL WELL/SPOILER DISC. PNL TO SPOILER #8-CHANNEL L2C | | | | | | | | | | | |
| 0001 | 20 | GA | | | 2-0 | 27-61-17 | D00655 | 10 | | | GD00560 | ST.. | E | | ALL |
| 4501RB | 20 | 7N | | AA | 23-0 | 27-61-17 | D40579J | 7 | | | D00655 | 7 | | | ALL |
| 4501WB | 20 | 7N | | AA | 0-0 | 27-61-17 | D40579J | 3 | | | D00655 | 1 | | | ALL |
| 4501WK | 20 | 7N | | AA | 0-0 | 27-61-17 | D40579J | 8 | | | D00655 | 8 | | | ALL |
| 4501WN | 20 | 7N | | AA | 0-0 | 27-61-17 | D40579J | 6 | | | D00655 | 6 | | | ALL |
| 4501WO | 20 | 7N | | AA | 0-0 | 27-61-17 | D40579J | 5 | | | D00655 | 5 | | | ALL |
| 4501WR | 20 | 7N | | AA | 0-0 | 27-61-17 | D40579J | 1 | | | D00655 | 3 | | | ALL |
| 4501WV | 20 | 7N | | AA | 0-0 | 27-61-17 | D40579J | 9 | | | D00655 | 9 | | | ALL |
| 4501Z | | | | AA | 0-0 | 27-61-17 | D40579J | S/R | | | GD00560 | ST.. | E | | ALL |
| W3406 | 286N3406 | | | RIGHT REAR SPAR DISC TO FUEL & FLIGHT CONTROLS | | | | | | | | | | | |
| 0001 | 20 | GA | | | 1-4 | 27-18-11 | D02066 | 1 | | | GD00276 | AC.. | E | | ALL |
| 0002 | 18 | GA | | | 1-9 | 28-26-11 | D01524 | 4 | | | GD00429 | DC.. | E | | ALL |
| 0003 | 18 | GA | | | 1-11 | 27-58-11 | D01802 | 4 | | | GD00423 | AC.. | E | | ALL |
| 0004 | 18 | GA | | | 2-3 | 28-41-31 | D02816 | 8 | | | GD00425 | DC.. | E | | 115-199 |
| 0005 | 18 | GA | | | 1-8 | 27-51-41 | D01802 | 5 | | | GD02425 | ST.. | E | | ALL |
| 0006 | 18 | GA | | | 1-11 | 28-42-11 | D01832 | 2 | 18 | | GD00431 | DC.. | E | | ALL |
| 0007 | 18 | GA | | | 2-0 | 28-41-41 | D02810 | 8 | | | GD00990 | DC.. | E | | 115-199 |
| 0008 | 18 | GA | | | 2-2 | 28-43-11 | SP01038 | | | | GD00203 | CAP | Y | | 115-199 |
| 0009 | 18 | GA | | | 1-5 | 28-22-11 | GD02386 | ST.. | E | | D01836 | 4 | | | ALL |
| 0011 | 18 | GA | | | 1-10 | 28-22-21 | GD00203 | DC.. | E | | D02022 | 4 | | | ALL |
| 0012 | 18 | GA | | | 1-11 | 28-22-21 | GD02419 | ST.. | E | | D02022 | 7 | | | ALL |
| 0013 | 18 | GA | | | 1-4 | 28-21-23 | D02444 | 3 | 18 | | GD02674 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3406 | 286N3406 | | | RIGHT REAR SPAR DISC TO FUEL & FLIGHT CONTROLS (continued) | | | | | | | | | | | |
| 0015 | 18 | | GA | | 1-6 | 28-26-11 | D01524 | 7 | | | GD00430 | ST.. | E | | ALL |
| 0018 | 18 | | GA | | 1-8 | 28-41-31 | D02816 | 10 | | | GD00428 | ST.. | E | | 115-199 |
| 0021 | 18 | | GA | | 1-5 | 28-42-11 | D01832 | 4 | 18 | | GD00432 | ST.. | E | | ALL |
| 0022 | 18 | | GA | | 2-1 | 28-41-41 | D02810 | 10 | | | GD00991 | ST.. | E | | 115-199 |
| 1003 | 20 | | GE | AV | 2-5 | 28-21-23 | D02444 | 1 | | | GD00425 | DC.. | E | *1 | 001-099 |
| 1003 | 20 | | GE | AV | 2-5 | 28-21-23 | D02444 | 1 | | | GD00425 | DC.. | E | * | 115-199 |
| 1003Z | | | | AV | 0-0 | 28-21-23 | GD02674 | ST.. | E | *1 | GD00425 | DC.. | E | *1 | 001-099 |
| 1003Z | | | | AV | 0-0 | 28-21-23 | GD02674 | ST.. | E | *1 | GD00425 | DC.. | E | * | 115-199 |
| 1004 | 20 | | GE | AW | 2-5 | 28-21-23 | D02444 | 4 | | | GD00425 | DC.. | E | *2 | 001-099 |
| 1004 | 20 | | GE | AW | 2-5 | 28-21-23 | D02444 | 4 | | | GD00425 | DC.. | E | * | 115-199 |
| 1004Z | | | | AW | 0-0 | 28-21-23 | GD02674 | ST.. | E | *1 | GD00425 | DC.. | E | *2 | 001-099 |
| 1004Z | | | | AW | 0-0 | 28-21-23 | GD02674 | ST.. | E | *1 | GD00425 | DC.. | E | * | 115-199 |
| 1006 | 20 | | GE | AL | 46-3 | 27-18-11 | D02066 | 2 | | | D40930J | 8 | | | 001-099 |
| 1006 | 20 | | GE | AL | 46-3 | 27-18-11 | D02066 | 2 | | | D40930P | 8 | | | 115-199 |
| 1006Z | | | | AL | 0-0 | 27-18-11 | GD02426 | ST.. | E | *1 | D40930J | S/R | | | 001-099 |
| 1006Z | | | | AL | 0-0 | 27-18-11 | GD02426 | ST.. | E | *1 | D40930P | S/R | | | 115-199 |
| 1016 | 20 | | GE | AD | 10-1 | 28-41-31 | D02816 | 5 | | | D40930P | 7 | | | 115-199 |
| 1016Z | | | | AD | 0-0 | 28-41-31 | GD00428 | ST.. | E | *2 | D40930P | S/R | | | 115-199 |
| 1019 | 18 | | GE | AR | 2-5 | 28-42-11 | D01832 | 3 | 18 | | D40930J | 23 | 18 | | 001-099 |
| 1019 | 18 | | GE | AR | 2-5 | 28-42-11 | D01832 | 3 | 18 | | D40930P | 23 | 18 | | 115-199 |
| 1019Z | | | | AR | 0-0 | 28-42-11 | GD00432 | ST.. | E | | D40930J | S/R | | | 001-099 |
| 1019Z | | | | AR | 0-0 | 28-42-11 | GD00432 | ST.. | E | | D40930P | S/R | | | 115-199 |
| 1024 | 20 | | GE | AF | 5-5 | 28-41-41 | D02810 | 5 | | | D40930P | 11 | | | 115-199 |
| 1024Z | | | | AF | 0-0 | 28-41-41 | GD00991 | ST.. | E | *1 | D40930P | S/R | | | 115-199 |
| 1025 | 20 | | GE | BC | 46-3 | 27-18-11 | D40930J | 36 | | | D02066 | 3 | | | 001-099 |
| 1025 | 20 | | GE | BC | 46-3 | 27-18-11 | D40930P | 36 | | | D02066 | 3 | | | 115-199 |
| 1025Z | | | | BC | 0-0 | 27-18-11 | D40930J | S/R | | | GD02426 | ST.. | E | | 001-099 |
| 1025Z | | | | BC | 0-0 | 27-18-11 | D40930P | S/R | | | GD02426 | ST.. | E | | 115-199 |
| 2501B | 20 | 2Z | AI | | 50-10 | 28-21-21 | D02456 | B | | | D40944J | 2 | | | 001-099 |
| 2501B | 20 | 2Z | AI | | 50-10 | 28-21-21 | D02456 | B | | | D40944P | 2 | | | 115-199 |
| 2501R | 20 | 2Z | AI | | 0-0 | 28-21-21 | D02456 | A | | | D40944J | 1 | | | 001-099 |
| 2501R | 20 | 2Z | AI | | 0-0 | 28-21-21 | D02456 | A | | | D40944P | 1 | | | 115-199 |
| 2501ZI | | | | AI | 0-0 | 28-21-21 | D02456 | C | | | D40944J | 3 | | | 001-099 |
| 2501ZI | | | | AI | 0-0 | 28-21-21 | D02456 | C | | | D40944P | 3 | | | 115-199 |
| 2501ZO | | | | AI | 0-0 | 28-21-21 | GD00267 | ST.. | E | | D40944J | S/R | | | 001-099 |
| 2501ZO | | | | AI | 0-0 | 28-21-21 | GD00267 | ST.. | E | | D40944P | S/R | | | 115-199 |
| 2502B | 20 | GF | AC | | 46-3 | 27-18-11 | D02066 | 4 | | | D40930J | 9 | | | 001-099 |
| 2502B | 20 | GF | AC | | 46-3 | 27-18-11 | D02066 | 4 | | | D40930P | 9 | | | 115-199 |
| 2502R | 20 | GF | AC | | 0-0 | 27-18-11 | D02066 | 5 | | | D40930J | 10 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|--|--|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | | | |
| W3406 | 286N3406 | | | RIGHT REAR SPAR DISC TO FUEL & FLIGHT CONTROLS (continued) | | | | | | | | | | | | | | | |
| 2502R | 20 | GF | AC | | 0-0 | 27-18-11 | D02066 | | 5 | | | D40930P | 10 | | | 115-199 | | | |
| 2502Z | | | AC | | 0-0 | 27-18-11 | GD02426 | ST.. | E | *1 | | D40930J | S/R | | | 001-099 | | | |
| 2502Z | | | AC | | 0-0 | 27-18-11 | GD02426 | ST.. | E | *1 | | D40930P | S/R | | | 115-199 | | | |
| 2504B | 20 | GF | AG | | 10-1 | 28-41-31 | D02816 | | 3 | | | D40930P | 4 | | | 115-199 | | | |
| 2504R | 20 | GF | AG | | 0-0 | 28-41-31 | D02816 | | 4 | | | D40930P | 3 | | | 115-199 | | | |
| 2504Z | | | AG | | 0-0 | 28-41-31 | GD00428 | ST.. | E | *2 | | D40930P | S/R | | | 115-199 | | | |
| 2505B | 20 | GF | AH | | 10-1 | 28-41-31 | D02816 | | 6 | | | D40930P | 6 | | | 115-199 | | | |
| 2505R | 20 | GF | AH | | 0-0 | 28-41-31 | D02816 | | 7 | | | D40930P | 5 | | | 115-199 | | | |
| 2505Z | | | AH | | 0-0 | 28-41-31 | GD00428 | ST.. | E | *2 | | D40930P | S/R | | | 115-199 | | | |
| 2506B | 20 | GF | AJ | | 5-5 | 28-41-41 | D02810 | | 3 | | | D40930P | 13 | | | 115-199 | | | |
| 2506R | 20 | GF | AJ | | 0-0 | 28-41-41 | D02810 | | 4 | | | D40930P | 12 | | | 115-199 | | | |
| 2506Z | | | AJ | | 0-0 | 28-41-41 | GD00991 | ST.. | E | *1 | | D40930P | S/R | | | 115-199 | | | |
| 2507B | 20 | GF | AK | | 5-5 | 28-41-41 | D02810 | | 6 | | | D40930P | 15 | | | 115-199 | | | |
| 2507R | 20 | GF | AK | | 0-0 | 28-41-41 | D02810 | | 7 | | | D40930P | 14 | | | 115-199 | | | |
| 2507Z | | | AK | | 0-0 | 28-41-41 | GD00991 | ST.. | E | *1 | | D40930P | S/R | | | 115-199 | | | |
| 2509B | 20 | GF | AS | | 9-5 | 28-21-23 | D02444 | | 2 | | | D40930J | 32 | | | 001-009 | | | |
| 2509B | 20 | GF | AS | | 9-5 | 28-21-23 | D02444 | | 2 | 16 | * | D40930J | 32 | | | 010-099 | | | |
| 2509B | 20 | GF | AS | | 9-5 | 28-21-23 | D02444 | | 2 | | | D40930P | 32 | | | 115-199 | | | |
| 2509R | 20 | GF | AS | | 0-0 | 28-21-23 | D02444 | | 5 | | | D40930J | 30 | | | 001-099 | | | |
| 2509R | 20 | GF | AS | | 0-0 | 28-21-23 | D02444 | | 5 | | | D40930P | 30 | | | 115-199 | | | |
| 2509Z | | | AS | | 0-0 | 28-21-23 | GD02674 | ST.. | E | *1 | | D40930J | S/R | | | 001-099 | | | |
| 2509Z | | | AS | | 0-0 | 28-21-23 | GD02674 | ST.. | E | *1 | | D40930P | S/R | | | 115-199 | | | |
| 2510B | 18 | GF | AP | | 11-6 | 28-43-11 | D40930J | | 25 | 18 | | SP01038 | | 9 | | 001-099 | | | |
| 2510B | 18 | GF | AP | | 11-6 | 28-43-11 | D40930P | | 25 | 18 | | SP01038 | | 9 | | 115-199 | | | |
| 2510R | 18 | GF | AP | | 0-0 | 28-43-11 | D40930J | | 27 | 18 | | SP01036 | | 9 | | 001-099 | | | |
| 2510R | 18 | GF | AP | | 0-0 | 28-43-11 | D40930P | | 27 | 18 | | SP01036 | | 9 | | 115-199 | | | |
| 2510Z | | | AP | | 0-0 | 28-43-11 | D40930J | S/R | | | | GD01397 | ST.. | E | | 001-099 | | | |
| 2510Z | | | AP | | 0-0 | 28-43-11 | D40930P | S/R | | | | GD01397 | ST.. | E | | 115-199 | | | |
| 2511B | 20 | GF | AB | | 40-3 | 27-51-61 | D01802 | | 13 | | | D40930J | 2 | | | 001-099 | | | |
| 2511B | 20 | GF | AB | | 40-3 | 27-51-61 | D01802 | | 13 | | | D40930P | 2 | | | 115-199 | | | |
| 2511R | 20 | GF | AB | | 0-0 | 27-51-61 | D01802 | | 12 | | | D40930J | 1 | | | 001-099 | | | |
| 2511R | 20 | GF | AB | | 0-0 | 27-51-61 | D01802 | | 12 | | | D40930P | 1 | | | 115-199 | | | |
| 2511Z | | | AB | | 0-0 | 27-51-61 | GD02425 | ST.. | E | * | | D40930J | S/R | | | 001-099 | | | |
| 2511Z | | | AB | | 0-0 | 27-51-61 | GD02425 | ST.. | E | * | | D40930P | S/R | | | 115-199 | | | |
| 2519B | 20 | GF | AM | | 42-2 | 27-51-41 | D01802 | | 7 | | | D40944J | 10 | | | 001-099 | | | |
| 2519B | 20 | GF | AM | | 42-2 | 27-51-41 | D01802 | | 7 | | | D40944P | 10 | | | 115-199 | | | |
| 2519R | 20 | GF | AM | | 0-0 | 27-51-41 | D01802 | | 6 | | | D40944J | 9 | | | 001-099 | | | |
| 2519R | 20 | GF | AM | | 0-0 | 27-51-41 | D01802 | | 6 | | | D40944P | 9 | | | 115-199 | | | |
| 2519Z | | | AM | | 0-0 | 27-51-41 | GD02425 | ST.. | E | | | D40944J | S/R | | | 001-099 | | | |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3406 | 286N3406 | | | RIGHT REAR SPAR DISC TO FUEL & FLIGHT CONTROLS (continued) | | | | | | | | | | | | |
| 2519Z | | | | AM | 0-0 | 27-51-41 | GD02425 | ST.. | E | | | D40944P | S/R | | 115-199 | |
| 3001B | 18 | GC | BA | | 4-2 | 28-22-11 | SP05018 | | 9 | | | D01836 | 3 | | 001-099 | |
| 3001B | 18 | GC | BA | | 5-0 | 28-22-11 | SP05018 | | 9 | | | D01836 | 3 | | 115-199 | |
| 3001R | 18 | GC | BA | | 0-0 | 28-22-11 | SP05014 | | 9 | | | D01836 | 1 | | ALL | |
| 3001Y | 18 | GC | BA | | 0-0 | 28-22-11 | SP05016 | | 9 | | | D01836 | 2 | | ALL | |
| 3501B | 20 | GG | AO | | 42-2 | 27-58-11 | D01802 | | 1 | | | D40944J | 7 | | 001-099 | |
| 3501B | 20 | GG | AO | | 42-2 | 27-58-11 | D01802 | | 1 | | | D40944P | 7 | | 115-199 | |
| 3501R | 20 | GG | AO | | 0-0 | 27-58-11 | D01802 | | 3 | | | D40944J | 8 | | 001-099 | |
| 3501R | 20 | GG | AO | | 0-0 | 27-58-11 | D01802 | | 3 | | | D40944P | 8 | | 115-199 | |
| 3501Y | 20 | GG | AO | | 0-0 | 27-58-11 | D01802 | | 2 | | | D40944J | 6 | | 001-099 | |
| 3501Y | 20 | GG | AO | | 0-0 | 27-58-11 | D01802 | | 2 | | | D40944P | 6 | | 115-199 | |
| 3501Z | | | | AO | 0-0 | 27-58-11 | GD02425 | ST.. | E | * | | D40944J | S/R | | 001-099 | |
| 3501Z | | | | AO | 0-0 | 27-58-11 | GD02425 | ST.. | E | * | | D40944P | S/R | | 115-199 | |
| 3503B | 20 | GG | AE | | 4-2 | 28-26-11 | D01524 | | 5 | | | D40930J | 20 | | 001-099 | |
| 3503B | 20 | GG | AE | | 4-2 | 28-26-11 | D01524 | | 5 | | | D40930P | 20 | | 115-199 | |
| 3503R | 20 | GG | AE | | 0-0 | 28-26-11 | D01524 | | 3 | | | D40930J | 22 | | 001-099 | |
| 3503R | 20 | GG | AE | | 0-0 | 28-26-11 | D01524 | | 3 | | | D40930P | 22 | | 115-199 | |
| 3503Y | 20 | GG | AE | | 0-0 | 28-26-11 | D01524 | | 2 | | | D40930J | 21 | | 001-099 | |
| 3503Y | 20 | GG | AE | | 0-0 | 28-26-11 | D01524 | | 2 | | | D40930P | 21 | | 115-199 | |
| 3503Z | | | | AE | 0-0 | 28-26-11 | GD00430 | ST.. | E | | | D40930J | S/R | | 001-099 | |
| 3503Z | | | | AE | 0-0 | 28-26-11 | GD00430 | ST.. | E | | | D40930P | S/R | | 115-199 | |
| 3504B | 20 | GG | BB | | 12-8 | 28-22-21 | D40942J | | 2 | | | D02022 | 2 | | 001-099 | |
| 3504B | 20 | GG | BB | | 12-8 | 28-22-21 | D40942P | | 2 | | | D02022 | 2 | | 115-199 | |
| 3504R | 20 | GG | BB | | 0-0 | 28-22-21 | D40942J | | 3 | | | D02022 | 5 | | 001-099 | |
| 3504R | 20 | GG | BB | | 0-0 | 28-22-21 | D40942P | | 3 | | | D02022 | 5 | | 115-199 | |
| 3504Y | 20 | GG | BB | | 0-0 | 28-22-21 | D40942J | | 1 | | | D02022 | 3 | | 001-099 | |
| 3504Y | 20 | GG | BB | | 0-0 | 28-22-21 | D40942P | | 1 | | | D02022 | 3 | | 115-199 | |
| 3504Z | | | | BB | 0-0 | 28-22-21 | D40942J | S/R | | | | GD02419 | ST.. | E | 001-099 | |
| 3504Z | | | | BB | 0-0 | 28-22-21 | D40942P | S/R | | | | GD02419 | ST.. | E | 115-199 | |
| 4251B | 20 | GH | AA | | 40-3 | 27-51-61 | D01802 | | 15 | | | D40930J | 17 | | 001-099 | |
| 4251B | 20 | GH | AA | | 40-3 | 27-51-61 | D01802 | | 15 | | | D40930P | 17 | | 115-199 | |
| 4251G | 20 | GH | AA | | 0-0 | 27-51-61 | D01802 | | 17 | | | D40930J | 19 | | 001-099 | |
| 4251G | 20 | GH | AA | | 0-0 | 27-51-61 | D01802 | | 17 | | | D40930P | 19 | | 115-199 | |
| 4251R | 20 | GH | AA | | 0-0 | 27-51-61 | D01802 | | 14 | | | D40930J | 16 | | 001-099 | |
| 4251R | 20 | GH | AA | | 0-0 | 27-51-61 | D01802 | | 14 | | | D40930P | 16 | | 115-199 | |
| 4251Y | 20 | GH | AA | | 0-0 | 27-51-61 | D01802 | | 16 | | | D40930J | 18 | | 001-099 | |
| 4251Y | 20 | GH | AA | | 0-0 | 27-51-61 | D01802 | | 16 | | | D40930P | 18 | | 115-199 | |
| 4251Z | | | | AA | 0-0 | 27-51-61 | GD02425 | ST.. | E | * | | D40930J | S/R | | 001-099 | |
| 4251Z | | | | AA | 0-0 | 27-51-61 | GD02425 | ST.. | E | * | | D40930P | S/R | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3406 | 286N3406 | | | RIGHT REAR SPAR DISC TO FUEL & FLIGHT CONTROLS (continued) | | | | | | | | | | | |
| 4252B | 20 | | GH | AN | 42-2 | 27-51-41 | D01802 | | 9 | | D40944J | 12 | | | 001-099 |
| 4252B | 20 | | GH | AN | 42-2 | 27-51-41 | D01802 | | 9 | | D40944P | 12 | | | 115-199 |
| 4252G | 20 | | GH | AN | 0-0 | 27-51-41 | D01802 | | 11 | | D40944J | 14 | | | 001-099 |
| 4252G | 20 | | GH | AN | 0-0 | 27-51-41 | D01802 | | 11 | | D40944P | 14 | | | 115-199 |
| 4252R | 20 | | GH | AN | 0-0 | 27-51-41 | D01802 | | 8 | | D40944J | 11 | | | 001-099 |
| 4252R | 20 | | GH | AN | 0-0 | 27-51-41 | D01802 | | 8 | | D40944P | 11 | | | 115-199 |
| 4252Y | 20 | | GH | AN | 0-0 | 27-51-41 | D01802 | | 10 | | D40944J | 13 | | | 001-099 |
| 4252Y | 20 | | GH | AN | 0-0 | 27-51-41 | D01802 | | 10 | | D40944P | 13 | | | 115-199 |
| 4252Z | | | | AN | 0-0 | 27-51-41 | GD02425 | ST.. | E | * | D40944J | S/R | | | 001-099 |
| 4252Z | | | | AN | 0-0 | 27-51-41 | GD02425 | ST.. | E | * | D40944P | S/R | | | 115-199 |
| A-01 | | | | AQ | 0-0 | 28-43-11 | TS5140 | = | A | | SP01038 | | 9 | | ALL |
| B-02 | | | | AQ | 0-0 | 28-43-11 | TS5140 | = | B | | SP01036 | | 9 | | ALL |
| T-B | | | | | 0-0 | 28-21-23 | R10412 | BLU | | | GD00425 | DC.. | E | | 010-099 |
| T-R | | | | | 0-0 | 28-21-23 | R10412 | RED | | | D02444 | 2 | 16 | * | 010-099 |
| W-B | | | | | 0-0 | SPARE | R10412 | CAP | Y | | R10412 | BLU | | | 010-099 |
| W-R | | | | | 0-0 | SPARE | R10412 | CAP | Y | | R10412 | RED | | | 010-099 |
| W3409 | 286N3409 | | | R. WHEEL WELL/SPOILER DISC. PNL TO SPOILER #7-CHANNEL L2B | | | | | | | | | | | |
| 0001 | 20 | | GA | | 2-0 | 27-61-18 | D00653 | | 10 | | GD00556 | ST.. | E | | ALL |
| 4501RB | 20 | | 7N | AA | 25-0 | 27-61-18 | D40591J | | 7 | | D00653 | 7 | | | ALL |
| 4501WB | 20 | | 7N | AA | 0-0 | 27-61-18 | D40591J | | 3 | | D00653 | 1 | | | ALL |
| 4501WK | 20 | | 7N | AA | 0-0 | 27-61-18 | D40591J | | 8 | | D00653 | 8 | | | ALL |
| 4501WN | 20 | | 7N | AA | 0-0 | 27-61-18 | D40591J | | 6 | | D00653 | 6 | | | ALL |
| 4501WO | 20 | | 7N | AA | 0-0 | 27-61-18 | D40591J | | 5 | | D00653 | 5 | | | ALL |
| 4501WR | 20 | | 7N | AA | 0-0 | 27-61-18 | D40591J | | 1 | | D00653 | 3 | | | ALL |
| 4501WV | 20 | | 7N | AA | 0-0 | 27-61-18 | D40591J | | 9 | | D00653 | 9 | | | ALL |
| 4501Z | | | | AA | 0-0 | 27-61-18 | D40591J | | S/R | | GD00556 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3400

Page 11 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3411 | | 286N3411 | | | | R.SPOILER/SPAR DISC. PNL TO SPOILER #11-CHANNEL R2A | | | | | | | | | |
| 0001 | 20 | GA | | | 2-0 | 27-61-14 | D00661 | 10 | | | GD00572 | ST.. | E | | ALL |
| 4501RB | 20 | 7N | AA | | 38-0 | 27-61-14 | D40519J | 7 | | | D00661 | 7 | | | 001-099 |
| 4501RB | 20 | 7N | AA | | 38-0 | 27-61-14 | D40519P | 7 | | | D00661 | 7 | | | 115-199 |
| 4501WB | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519J | 3 | | | D00661 | 1 | | | 001-099 |
| 4501WB | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519P | 3 | | | D00661 | 1 | | | 115-199 |
| 4501WK | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519J | 8 | | | D00661 | 8 | | | 001-099 |
| 4501WK | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519P | 8 | | | D00661 | 8 | | | 115-199 |
| 4501WN | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519J | 6 | | | D00661 | 6 | | | 001-099 |
| 4501WN | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519P | 6 | | | D00661 | 6 | | | 115-199 |
| 4501WO | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519J | 5 | | | D00661 | 5 | | | 001-099 |
| 4501WO | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519P | 5 | | | D00661 | 5 | | | 115-199 |
| 4501WR | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519J | 1 | | | D00661 | 3 | | | 001-099 |
| 4501WR | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519P | 1 | | | D00661 | 3 | | | 115-199 |
| 4501WV | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519J | 9 | | | D00661 | 9 | | | 001-099 |
| 4501WV | 20 | 7N | AA | | 0-0 | 27-61-14 | D40519P | 9 | | | D00661 | 9 | | | 115-199 |
| 4501Z | | | AA | | 0-0 | 27-61-14 | D40519J | | S/R | | GD00572 | ST.. | E | | 001-099 |
| 4501Z | | | AA | | 0-0 | 27-61-14 | D40519P | | S/R | | GD00572 | ST.. | E | | 115-199 |
| W3412 | | 286N3412 | | | | R ENG F/W DISC TO P32 PANEL,GENERATOR FEEDERS | | | | | | | | | |
| 0001 | *2 | 43 | | | 61-8 | 24-21-21 | C00903 | T1 | H* | | SM00001 | | GX | | ALL |
| 0002 | *2 | 43 | | | 61-8 | 24-21-21 | C00903 | T2 | H* | | SM00002 | | GX | | ALL |
| 0003 | *2 | 43 | | | 61-8 | 24-21-21 | C00903 | T3 | H* | | SM00003 | | GX | | ALL |
| 0004 | *1 | CQ | | | 14-3 | 24-21-21 | SM00004 | | GX | | D01216P | A | | | ALL |
| 0005 | *1 | CQ | | | 14-3 | 24-21-21 | SM00005 | | GX | | D01216P | B | | | ALL |
| 0006 | *1 | CQ | | | 14-3 | 24-21-21 | SM00006 | | GX | | D01216P | C | | | ALL |
| 0007 | 04 | CQ | | | 4-0 | 24-21-21 | GD00241 | AC.. | H7 | | D01216P | D | | | ALL |
| 0008 | *2 | 43 | | | 1-3 | 24-21-21 | SM00001 | | GX | | SM00004 | | GX | | ALL |
| 0009 | *2 | 43 | | | 1-3 | 24-21-21 | SM00002 | | GX | | SM00005 | | GX | | ALL |
| 0010 | *2 | 43 | | | 1-3 | 24-21-21 | SM00003 | | GX | | SM00006 | | GX | | ALL |
| W3414 | | 286N3414 | | | | R. W/B DISC. TO R. ENG F/W R. ENG/GEN CONTROL | | | | | | | | | |
| 0001 | 20 | GA | | | 20-7 | 24-11-21 | D40290P | 8 | | | D40028J | 8 | | | ALL |
| 0002 | 16 | GA | | | 20-7 | 24-11-21 | D40290P | 4 | | | D40028J | 4 | | | ALL |
| 0006 | 20 | GA | | | 20-7 | SPARE | D40290P | 25 | | | D40028J | 25 | | | ALL |
| 0007 | 20 | GA | | | 20-7 | SPARE | D40290P | 26 | | | D40028J | 26 | | | ALL |
| 2001B | 20 | GB | AD | | 20-7 | 24-11-21 | D40290P | 18 | | | D40028J | 18 | | | ALL |
| 2001R | 20 | GB | AD | | 0-0 | 24-11-21 | D40290P | 19 | | | D40028J | 19 | | | ALL |
| 2002B | 20 | GB | AE | | 20-7 | 24-11-21 | D40290P | 6 | | | D40028J | 6 | | | ALL |
| 2002R | 20 | GB | AE | | 0-0 | 24-11-21 | D40290P | 7 | | | D40028J | 7 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3410

Page 1

May 17/2006



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | |
|------------|-------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|-------------|------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| Wire No. | | | | | | | | | | | | | | | |
| | | | | | | | | | | | | | | | |
| W3416 | 286N3416 | | | | R. ENGINE T/R CONT F/W DISC TO STRUT DISC (continued) | | | | | | | | | | |
| 2001B | 20 | FB | AA | | 4-11 | 78-34-21 | D40272J | | 2 | | D01220J | | 3 | | ALL |
| 2001R | 20 | FB | AA | | 0-0 | 78-34-21 | D40272J | | 1 | | D01220J | | 1 | | ALL |
| 2002B | 20 | FB | AB | | 4-11 | 78-34-21 | D40272J | | 4 | | D01220J | | 6 | | ALL |
| 2002R | 20 | FB | AB | | 0-0 | 78-34-21 | D40272J | | 3 | | D01220J | | 4 | | ALL |
| 2003B | 20 | FB | AC | | 4-11 | SPARE | D40272J | | 6 | | D01220J | | 5 | | ALL |
| 2003R | 20 | FB | AC | | 0-0 | SPARE | D40272J | | 5 | | D01220J | | 7 | | ALL |
| | | | | | | | | | | | | | | | |
| W3418 | 286N3418 | | | | R ENGINE T/R IND F/W DISC TO STRUT DISC | | | | | | | | | | |
| 2001B | 20 | FB | AA | | 4-1 | 78-36-21 | D40278J | | 2 | | D01218J | | 2 | | ALL |
| 2001R | 20 | FB | AA | | 0-0 | 78-36-21 | D40278J | | 1 | | D01218J | | 1 | | ALL |
| 2002B | 20 | FB | AB | | 4-1 | 78-36-21 | D40278J | | 4 | | D01218J | | 6 | | ALL |
| 2002R | 20 | FB | AB | | 0-0 | 78-36-21 | D40278J | | 3 | | D01218J | | 5 | | ALL |
| 2003B | 20 | FB | AC | | 4-1 | 78-36-21 | D40278J | | 6 | | D01218J | | 4 | | ALL |
| 2003R | 20 | FB | AC | | 0-0 | 78-36-21 | D40278J | | 5 | | D01218J | | 3 | | ALL |
| 2004B | 20 | FB | AD | | 4-1 | 78-36-21 | D40278J | | 8 | | D01218J | | 8 | | ALL |
| 2004R | 20 | FB | AD | | 0-0 | 78-36-21 | D40278J | | 7 | | D01218J | | 7 | | ALL |
| 2501B | 16 | FF | MN | | 4-1 | 78-34-61 | D40278J | | 10 | | D01218J | | 10 | | ALL |
| 2501R | 16 | FF | MN | | 0-0 | 78-34-61 | D40278J | | 9 | | D01218J | | 9 | | ALL |
| 2501Z | | | MN | | 0-0 | 78-34-61 | D40278J | | S/R | | D01218J | | S/R | | ALL |
| | | | | | | | | | | | | | | | |
| W3419 | 286N3419 | | | | R. AFT BODY/SPAR DISC. PNL TO SPOILER #9-CHANNEL R2B | | | | | | | | | | |
| 0001 | 20 | GA | | | 2-0 | 27-61-16 | D00657 | | 10 | | GD00564 | ST.. | E | | ALL |
| 4501RB | 20 | 7N | AA | | 27-0 | 27-61-16 | D40571J | | 7 | | D00657 | 7 | | | 001-099 |
| 4501RB | 20 | 7N | AA | | 27-0 | 27-61-16 | D40571P | | 7 | | D00657 | 7 | | | 115-199 |
| 4501WB | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571J | | 3 | | D00657 | 1 | | | 001-099 |
| 4501WB | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571P | | 3 | | D00657 | 1 | | | 115-199 |
| 4501WK | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571J | | 8 | | D00657 | 8 | | | 001-099 |
| 4501WK | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571P | | 8 | | D00657 | 8 | | | 115-199 |
| 4501WN | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571J | | 6 | | D00657 | 6 | | | 001-099 |
| 4501WN | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571P | | 6 | | D00657 | 6 | | | 115-199 |
| 4501WO | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571J | | 5 | | D00657 | 5 | | | 001-099 |
| 4501WO | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571P | | 5 | | D00657 | 5 | | | 115-199 |
| 4501WR | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571J | | 1 | | D00657 | 3 | | | 001-099 |
| 4501WR | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571P | | 1 | | D00657 | 3 | | | 115-199 |
| 4501WV | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571J | | 9 | | D00657 | 9 | | | 001-099 |
| 4501WV | 20 | 7N | AA | | 0-0 | 27-61-16 | D40571P | | 9 | | D00657 | 9 | | | 115-199 |
| 4501Z | | | AA | | 0-0 | 27-61-16 | D40571J | | S/R | | GD00564 | ST.. | E | | 001-099 |
| 4501Z | | | AA | | 0-0 | 27-61-16 | D40571P | | S/R | | GD00564 | ST.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3410

Page 3 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|------------------------|------------------------|------------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W3420 | 286N3420 | RIGHT STRUT DISC TO RIGHT FRONT/SPAR DISC - T/R CONTROL | | | |
| 0001 | 20 GK | 30-6 36-11-21 | D40274P 7 | D40272P 7 | ALL |
| 0002 | 20 GK | 21-11 26-11-22 | D40274P 8 | D41164P 5 | ALL |
| 0003 | 20 GK | 21-11 26-11-22 | D40274P 12 | D41164P 2 | ALL |
| 0004 | 18 GK | 1-3 26-12-21 | S10203 =2 C | GD00232 DC.. E | ALL |
| 0005 | 18 GK | 26-10 26-12-21 | D40274P 10 | S10203 =1 C | * ALL |
| 0006 | 18 GK | 5-0 26-12-21 | S10204 =2 C | GD00249 DC.. E | ALL |
| 0007 | 18 GK | 4-4 26-12-21 | S10203 =1 C | S10204 =1 C | * ALL |
| 0008 | 18 GK | 10-5 26-12-21 | D41164P 3 | S10204 =1 C | * ALL |
| 0009 | 18 GK | 21-11 26-12-21 | D41164P 4 | D40274P 11 | ALL |
| 2001B | 20 GL AA | 30-6 78-34-21 | D40274P 2 | D40272P 2 | ALL |
| 2001R | 20 GL AA | 0-0 78-34-21 | D40274P 1 | D40272P 1 | ALL |
| 2002B | 20 GL AB | 30-6 78-34-21 | D40274P 4 | D40272P 4 | ALL |
| 2002R | 20 GL AB | 0-0 78-34-21 | D40274P 3 | D40272P 3 | ALL |
| 2003B | 20 GL AC | 30-6 SPARE | D40274P 6 | D40272P 6 | ALL |
| 2003R | 20 GL AC | 0-0 SPARE | D40274P 5 | D40272P 5 | ALL |
| YAAA | | 0-0 78-34-21 | GD03110 ST.. E | D40274P S/R | ALL |
| W3422 | 286N3422 | RIGHT STRUT DISC TO RIGHT FRONT/SPAR DISC - T/R INDICATION | | | |
| 2001B | 20 GL AA | 28-0 78-36-21 | D40280P 2 | D40278P 2 | 001-002, 115-199 |
| 2001B | 20 GL AA | 27-11 78-36-21 | D40280P 2 | D40278P 2 | 003-099 |
| 2001R | 20 GL AA | 0-0 78-36-21 | D40280P 1 | D40278P 1 | ALL |
| 2002B | 20 GL AB | 28-0 78-36-21 | D40280P 4 | D40278P 4 | 001-002, 115-199 |
| 2002B | 20 GL AB | 27-11 78-36-21 | D40280P 4 | D40278P 4 | 003-099 |
| 2002R | 20 GL AB | 0-0 78-36-21 | D40280P 3 | D40278P 3 | ALL |
| 2003B | 20 GL AC | 28-0 78-36-21 | D40280P 6 | D40278P 6 | 001-002, 115-199 |
| 2003B | 20 GL AC | 27-11 78-36-21 | D40280P 6 | D40278P 6 | 003-099 |
| 2003R | 20 GL AC | 0-0 78-36-21 | D40280P 5 | D40278P 5 | ALL |
| 2004B | 20 GL AD | 28-0 78-36-21 | D40280P 8 | D40278P 8 | 001-002, 115-199 |
| 2004B | 20 GL AD | 27-11 78-36-21 | D40280P 8 | D40278P 8 | 003-099 |
| 2004R | 20 GL AD | 0-0 78-36-21 | D40280P 7 | D40278P 7 | ALL |
| 2501B | 16 HQ MN | 29-0 78-34-61 | D41458P 4 | D40278P 10 | ALL |
| 2501R | 16 HQ MN | 0-0 78-34-61 | D41458P 3 | D40278P 9 | ALL |
| 2501Z | | 0-0 78-34-61 | D41458P 5 | D40278P S/R | ALL |
| YAAA | | 0-0 78-36-21 | GD03074 ST.. E | D40280P S/R | ALL |
| YBBB | | 0-0 78-34-61 | GD03088 ST.. E | D41458P S/R | 001-002, 115-199 |
| YBBB | | 0-0 78-34-61 | D41458P S/R | GD03088 ST.. E | 003-099 |
| W3424 | 286N3424 | WING BODY TO VAPOR BARRIER-RIGHT. | | | |
| 0001 | 20 GA | 26-10 33-43-12 | D40402P 18 | D41396P 8 | ALL |

WIRE LIST

D280N032

91-21-11

Section W3420

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3424 | 286N3424 | | | | WING BODY TO VAPOR BARRIER-RIGHT. (continued) | | | | | | | | | | | |
| 0003 | 20 | | GA | | 26-7 | SPARE | | D40402P | | 6 | | D41196P | | 16 | | 115-199 |
| 0004 | 20 | | GA | | 26-7 | SPARE | | D40402P | | 7 | | D41196P | | 17 | | 115-199 |
| 0005 | 20 | | GA | | 26-10 | 33-44-21 | | D40402P | | 5 | | D41396P | | 10 | | ALL |
| 0010 | 20 | | GA | | 26-7 | SPARE | | D40402P | | 13 | | D41196P | | 18 | | 115-199 |
| 0011 | 20 | | GA | | 26-7 | SPARE | | D40402P | | 11 | | D41196P | | 19 | | 115-199 |
| 0019 | 12 | | GA | | 2-6 | 33-42-12 | | D02292 | | 2 | | GD00236 | ST.. | E | | ALL |
| 1001 | 12 | | HE | AI | 2-2 | 33-42-12 | | D02292 | | 8 | | GD00235 | AC.. | E | *1 | ALL |
| 1001Z | | | | AI | 0-0 | 33-42-12 | | GD02679 | ST.. | E | | GD00235 | AC.. | E | *1 | ALL |
| 1002 | 12 | | HE | AJ | 3-0 | 33-42-12 | | D02292 | | 3 | | L00357 | =P | M | | ALL |
| 1002Z | | | | AJ | 0-0 | 33-42-12 | | GD02679 | ST.. | E | * | GD00236 | ST.. | E | *1 | ALL |
| 1003 | 12 | | HE | AK | 1-11 | 33-42-12 | | L00357 | =G | M | | GD00235 | AC.. | E | *2 | ALL |
| 1003Z | | | | AK | 0-0 | 33-42-12 | | GD00236 | ST.. | E | *1 | GD00235 | AC.. | E | *2 | ALL |
| 1004 | 20 | | GE | AL | 16-6 | 27-81-31 | | D41198P | | 22 | | SP02196 | | 9 | | ALL |
| 1004Z | | | | AL | 0-0 | 27-81-31 | | D41198P | S/R | | | GD04198 | DC.. | E | *2 | ALL |
| 1005 | 20 | | GE | AM | 13-2 | 27-81-31 | | D41396P | | 11 | | SP02196 | | 9 | | ALL |
| 1005Z | | | | AM | 0-0 | 27-81-31 | | D41396P | S/R | | | GD04198 | DC.. | E | *2 | ALL |
| 2001B | 20 | | GB | AA | 26-8 | 27-51-61 | | D41198P | | 17 | | D41396P | | 3 | | ALL |
| 2001R | 20 | | GB | AA | 0-0 | 27-51-61 | | D41198P | | 16 | | D41396P | | 2 | | ALL |
| 2501B | 20 | | GF | AH | 7-11 | 33-42-12 | | D40402P | | 4 | | D02292 | | 5 | | ALL |
| 2501R | 20 | | GF | AH | 0-0 | 33-42-12 | | D40402P | | 3 | | D02292 | | 7 | | ALL |
| 2501Z | | | | AH | 0-0 | 33-42-12 | | D40402P | S/R | | | GD02679 | ST.. | E | * | ALL |
| 4001B | 20 | | GD | AB | 26-8 | 27-51-61 | | D41198P | | 18 | | D41396P | | 4 | | ALL |
| 4001G | 20 | | GD | AB | 0-0 | 27-51-61 | | D41198P | | 21 | | D41396P | | 7 | | ALL |
| 4001R | 20 | | GD | AB | 0-0 | 27-51-61 | | D41198P | | 19 | | D41396P | | 5 | | ALL |
| 4001Y | 20 | | GD | AB | 0-0 | 27-51-61 | | D41198P | | 20 | | D41396P | | 6 | | ALL |
| 4501AA | 20 | | 4K | AF | 26-5 | SPARE | | D41198P | | 14 | | D41196P | | 14 | | 115-199 |
| 4501RB | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 5 | | D41196P | | 5 | | 115-199 |
| 4501RG | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 4 | | D41196P | | 4 | | 115-199 |
| 4501RK | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 3 | | D41196P | | 3 | | 115-199 |
| 4501RV | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 7 | | D41196P | | 7 | | 115-199 |
| 4501RY | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 2 | | D41196P | | 2 | | 115-199 |
| 4501W | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 1 | | D41196P | | 1 | | 115-199 |
| 4501WB | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 13 | | D41196P | | 13 | | 115-199 |
| 4501WG | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 12 | | D41196P | | 12 | | 115-199 |
| 4501WK | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 6 | | D41196P | | 6 | | 115-199 |
| 4501WN | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 8 | | D41196P | | 8 | | 115-199 |
| 4501WO | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 11 | | D41196P | | 11 | | 115-199 |
| 4501WR | 20 | | 4K | AF | 0-0 | 28-41-31 | | D41198P | | 9 | | D41196P | | 9 | | 115-199 |
| 4501WV | 20 | | 4K | AF | 0-0 | SPARE | | D41198P | | 15 | | D41196P | | 15 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3420

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | | |
|------------|-------------|----|----|-------------|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3424 | 286N3424 | | | | WING BODY TO VAPOR BARRIER-RIGHT. (continued) | | | | | | | | | | | |
| 4501WY | 20 | 4K | | AF | 0-0 | 28-41-31 | D41198P | 10 | | | D41196P | 10 | | | 115-199 | |
| 4501Z | | | | AF | 0-0 | 28-41-31 | D41198P | S/R | | | D41196P | S/R | | | 115-199 | |
| A-B | | | | | 0-0 | 27-81-31 | S10588 | 3 | | | SP02196 | CAP | Y | | ALL | |
| A-C | | | | | 0-0 | 27-81-31 | S10588 | 1 | | | GD04198 | DC.. | E | | ALL | |
| A-D | | | | | 0-0 | 27-81-31 | S10588 | 2 | | | SP02196 | | 9 | | ALL | |
| YAAD | | | | | 0-0 | 27-51-61 | GD03074 | ST.. | E | *2 | D41198P | S/R | | | ALL | |
| YAAF | | | | | 0-0 | 33-43-12 | GD03074 | ST.. | E | *2 | D40402P | S/R | | | ALL | |
| W3426 | 286N3426 | | | | VAPOR BARRIER TO WING TIP-RIGHT | | | | | | | | | | | |
| 0002 | 20 | | GA | | 0-7 | 33-43-12 | D41396J | 8 | | | SM00009 | | 9 | | ALL | |
| 0003 | 20 | | GA | | 1-7 | 28-41-11 | D40326J | 26 | | | GD00440 | DC.. | E | * | 001-099 | |
| 0003 | 20 | | GA | | 2-0 | 28-41-11 | D40326J | 26 | | | GD00440 | DC.. | E | *1 | 115-199 | |
| 0004 | 18 | | GA | | 4-9 | 28-21-11 | SP00578 | | 9 | | GD00440 | DC.. | E | | ALL | |
| 0005 | 20 | | GA | | 1-7 | 28-41-11 | D40326J | 33 | | | GD00440 | DC.. | E | * | 001-099 | |
| 0005 | 20 | | GA | | 1-7 | 28-41-11 | D40326J | 33 | | | GD00440 | DC.. | E | *1 | 115-199 | |
| 0006 | 20 | | GA | | 1-5 | 28-41-11 | D40326J | 34 | | | GD00443 | ST.. | E | *1 | ALL | |
| 0007 | 18 | | GA | | 1-7 | 33-44-21 | D00020 | 3 | | | GD01333 | ST.. | E | | ALL | |
| 0008 | 18 | | GA | | 1-5 | 27-51-41 | D01805 | 13 | | | GD01335 | ST.. | E | | ALL | |
| 0009 | 20 | | GA | | 1-7 | 28-21-23 | D40326J | 37 | | | GD00440 | DC.. | E | | ALL | |
| 0014 | 18 | | GA | | 1-10 | 33-43-12 | SP02872 | REF | | FB | GD01328 | ST.. | E | | ALL | |
| 0015 | 20 | | GA | | 1-5 | 28-21-22 | D40326J | 31 | | | GD00443 | ST.. | E | *1 | ALL | |
| 0016 | 20 | | GA | | 1-5 | 28-41-11 | D40326J | 35 | | | GD00443 | ST.. | E | *1 | ALL | |
| 0017 | 20 | | GA | | 1-5 | 28-41-11 | D40326J | 36 | | | GD00443 | ST.. | E | *1 | ALL | |
| 0018 | 18 | | GA | | 1-6 | 28-21-11 | GD00434 | DC.. | E | | D40324J | 24 | 18 | | ALL | |
| 1001 | 20 | | GE | AA | 30-2 | 27-81-31 | SP01116 | | 9 | | D41396J | 11 | | | ALL | |
| 1001Z | | | | AA | 0-0 | 27-81-31 | GD01829 | DC.. | E | | D41396J | S/R | | | ALL | |
| 1005 | 20 | | GE | BN | 16-1 | 28-26-11 | D40328J | 6 | | | D40324J | 6 | | | ALL | |
| 1005Z | | | | BN | 0-0 | 28-26-11 | D40328J | S/R | | | GD00433 | ST.. | E | *1 | ALL | |
| 1006 | 20 | | GE | AE | 19-5 | 28-21-11 | D40330J | 7 | | | SP00576 | | 9 | | ALL | |
| 1006Z | | | | AE | 0-0 | 28-21-11 | D40330J | S/R | | | SP00576 | REF | | AC | ALL | |
| 1007 | 20 | | GE | AT | 19-5 | 28-21-11 | SP00580 | | 9 | | D40330J | 5 | | | 001-099 | |
| 1007 | 20 | | GE | AT | 4-5 | 28-21-11 | SP00580 | | 9 | | D40326J | 43 | | | 115-199 | |
| 1007Z | | | | AT | 0-0 | 28-21-11 | GD00443 | ST.. | E | | D40330J | S/R | | | 001-099 | |
| 1007Z | | | | AT | 0-0 | 28-21-11 | GD00443 | ST.. | E | | GD00433 | ST.. | E | *4 | 115-199 | |
| 1008 | 20 | | GE | AW | 16-3 | 28-21-11 | D40330J | 6 | | | D40326J | 6 | | | 115-199 | |
| 1008Z | | | | AW | 0-0 | 28-21-11 | D40330J | S/R | | | GD00443 | ST.. | E | *3 | 115-199 | |
| 1009 | 20 | | GE | BA | 16-3 | 28-41-11 | D40330J | 9 | | | D40326J | 9 | | | 115-199 | |
| 1009Z | | | | BA | 0-0 | 28-41-11 | D40330J | S/R | | | GD02609 | ST.. | E | *1 | 115-199 | |
| 1010 | 20 | | GE | BB | 16-3 | 28-41-11 | D40330J | 20 | | | D40326J | 20 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W3420

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | To | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3426 | 286N3426 | | | VAPOR BARRIER TO WING TIP-RIGHT (continued) | | | | | | | | | | | |
| 1010Z | | | | BB | 0-0 | 28-41-11 | D40330J | S/R | | | GD02609 | ST.. | E | *1 | ALL |
| 1011 | 20 | GE | | BC | 16-3 | SPARE | D40330J | 21 | | | D40326J | 21 | | | 115-199 |
| 1011Z | | | | BC | 0-0 | SPARE | D40330J | S/R | | | GD02609 | ST.. | E | *1 | 115-199 |
| 1012 | 20 | GE | | AX | 16-3 | 28-21-11 | D40330J | 6 | | | D40326J | 5 | | | 001-099 |
| 1012 | 20 | GE | | AX | 16-3 | 28-21-11 | D40330J | 5 | | | D40326J | 5 | | | 115-199 |
| 1012Z | | | | AX | 0-0 | 28-21-11 | D40330J | S/R | | | GD00443 | ST.. | E | *4 | ALL |
| 1013 | 20 | GE | | AK | 16-1 | 28-21-11 | D40328J | 17 | | | D40324J | 17 | | | ALL |
| 1013Z | | | | AK | 0-0 | 28-21-11 | D40328J | S/R | | | GD00433 | ST.. | E | *1 | ALL |
| 1014 | 20 | GE | | BD | 16-3 | 28-41-11 | D40330J | 14 | | | D40326J | 14 | | | ALL |
| 1014Z | | | | BD | 0-0 | 28-41-11 | D40330J | S/R | | | GD02609 | ST.. | E | *1 | ALL |
| 1015 | 20 | GE | | BE | 16-3 | SPARE | D40330J | 15 | | | D40326J | 15 | | | 115-199 |
| 1015Z | | | | BE | 0-0 | SPARE | D40330J | S/R | | | GD02609 | ST.. | E | *2 | 115-199 |
| 2501B | 20 | GF | | BF | 16-3 | SPARE | D40330J | 48 | | | D40326J | 48 | | | ALL |
| 2501R | 20 | GF | | BF | 0-0 | SPARE | D40330J | 49 | | | D40326J | 49 | | | ALL |
| 2501Z | | | | BF | 0-0 | SPARE | D40330J | S/R | | | GD00443 | ST.. | E | *3 | ALL |
| 2502B | 20 | GF | | BG | 16-3 | SPARE | D40330J | 50 | | | D40326J | 50 | | | ALL |
| 2502R | 20 | GF | | BG | 0-0 | SPARE | D40330J | 51 | | | D40326J | 51 | | | ALL |
| 2502Z | | | | BG | 0-0 | SPARE | D40330J | S/R | | | GD00443 | ST.. | E | *3 | ALL |
| 2503B | 20 | GF | | AC | 16-3 | SPARE | D40330J | 52 | | | D40326J | 52 | | | ALL |
| 2503R | 20 | GF | | AC | 0-0 | SPARE | D40330J | 53 | | | D40326J | 53 | | | ALL |
| 2503Z | | | | AC | 0-0 | SPARE | D40330J | S/R | | | GD00443 | ST.. | E | *4 | ALL |
| 2504B | 20 | GF | | AD | 16-3 | SPARE | D40330J | 54 | | | D40326J | 54 | | | ALL |
| 2504R | 20 | GF | | AD | 0-0 | SPARE | D40330J | 55 | | | D40326J | 55 | | | ALL |
| 2504Z | | | | AD | 0-0 | SPARE | D40330J | S/R | | | GD00443 | ST.. | E | *4 | ALL |
| 2505B | 20 | GF | | AG | 16-1 | 28-26-11 | D40328J | 4 | | | D40324J | 4 | | | ALL |
| 2505R | 20 | GF | | AG | 0-0 | 28-26-11 | D40328J | 5 | | | D40324J | 5 | | | ALL |
| 2505Z | | | | AG | 0-0 | 28-26-11 | D40328J | S/R | | | GD00433 | ST.. | E | *2 | ALL |
| 2506B | 12 | HF | | AF | 49-1 | 33-43-12 | SM00009 | | 9 | | SP02874 | | 9 | | ALL |
| 2506R | 12 | HF | | AF | 0-0 | 33-43-12 | GD01331 | AC.. | E | | SP02872 | | 9 | | ALL |
| 2506Z | | | | AF | 0-0 | 33-43-12 | D41396J | S/R | | | SP02872 | REF | | FB | ALL |
| 2507B | 20 | GF | | BH | 16-3 | SPARE | D40330J | 13 | | | D40326J | 13 | | | 115-199 |
| 2507R | 20 | GF | | BH | 0-0 | SPARE | D40330J | 12 | | | D40326J | CAP | Y | | 115-199 |
| 2507Z | | | | BH | 0-0 | SPARE | D40330J | S/R | | | GD02609 | ST.. | E | *2 | 115-199 |
| 2509B | 18 | GF | | AR | 50-8 | 33-44-21 | D00020 | 1 | | | D41396J | 10 | | | ALL |
| 2509R | 18 | GF | | AR | 0-0 | 33-44-21 | D00020 | 2 | | | GD01960 | AC.. | E | | ALL |
| 2509Z | | | | AR | 0-0 | 33-44-21 | GD01333 | ST.. | E | | D41396J | S/R | | | ALL |
| 2510B | 20 | GF | | AL | 47-3 | 27-51-41 | D01805 | 2 | | | D40404J | 3 | | | ALL |
| 2510R | 20 | GF | | AL | 0-0 | 27-51-41 | D01805 | 1 | | | D40404J | 2 | | | ALL |
| 2510Z | | | | AL | 0-0 | 27-51-41 | GD01335 | ST.. | E | * | D40404J | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3420

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3426 | 286N3426 | | | VAPOR BARRIER TO WING TIP-RIGHT (continued) | | | | | | | | | | | |
| 2511B | 20 | GF | AN | | 47-8 | 27-51-61 | D01805 | 8 | | | D41396J | 3 | | | ALL |
| 2511R | 20 | GF | AN | | 0-0 | 27-51-61 | D01805 | 7 | | | D41396J | 2 | | | ALL |
| 2511Z | | | AN | | 0-0 | 27-51-61 | GD01335 | ST.. | E | * | D41396J | S/R | | | ALL |
| 2512B | 20 | GF | BO | | 16-1 | SPARE | D40328J | 18 | | | D40324J | 18 | | | ALL |
| 2512R | 20 | GF | BO | | 0-0 | SPARE | D40328J | 19 | | | D40324J | 19 | | | ALL |
| 2512Z | | | BO | | 0-0 | SPARE | D40328J | S/R | | | GD00433 | ST.. | E | *1 | ALL |
| 2513B | 20 | GF | AS | | 16-1 | 28-26-11 | D40328J | 2 | | | D40324J | 2 | | | ALL |
| 2513R | 20 | GF | AS | | 0-0 | 28-26-11 | D40328J | 3 | | | D40324J | 3 | | | ALL |
| 2513Z | | | AS | | 0-0 | 28-26-11 | D40328J | S/R | | | GD00433 | ST.. | E | *1 | ALL |
| 2514B | 20 | GF | AJ | | 16-1 | 28-21-21 | D40328J | 15 | | | D40324J | 15 | | | ALL |
| 2514R | 20 | GF | AJ | | 0-0 | 28-21-21 | D40328J | 16 | | | D40324J | 16 | | | ALL |
| 2514Z | | | AJ | | 0-0 | 28-21-21 | D40328J | S/R | | | GD00433 | ST.. | E | *2 | ALL |
| 2515B | 20 | GF | AI | | 16-3 | 28-41-11 | D40330J | 11 | | | D40326J | 11 | | | ALL |
| 2515R | 20 | GF | AI | | 0-0 | 28-41-11 | D40330J | 10 | | | D40326J | 10 | | | ALL |
| 2515Z | | | AI | | 0-0 | 28-41-11 | D40330J | S/R | | | D40326J | | | AA | ALL |
| 2516B | 20 | GF | BI | | 16-3 | SPARE | D40330J | 17 | | | D40326J | CAP | Y | | 115-199 |
| 2516R | 20 | GF | BI | | 0-0 | SPARE | D40330J | 16 | | | D40326J | 16 | | | 115-199 |
| 2516Z | | | BI | | 0-0 | SPARE | D40330J | S/R | | | GD02609 | ST.. | E | *2 | 115-199 |
| 2517B | 20 | GF | BJ | | 16-3 | 28-41-11 | D40330J | 19 | | | D40326J | 19 | | | ALL |
| 2517R | 20 | GF | BJ | | 0-0 | 28-41-11 | D40330J | 18 | | | D40326J | 18 | | | ALL |
| 2517Z | | | BJ | | 0-0 | 28-41-11 | D40330J | S/R | | | D40326J | | | BB | ALL |
| 2518B | 20 | GF | AO | | 16-3 | 28-21-22 | D40330J | 23 | | | D40326J | 38 | | | 115-199 |
| 2518R | 20 | GF | AO | | 0-0 | 28-21-22 | D40330J | 22 | | | D40326J | 42 | | | 115-199 |
| 2518Z | | | AO | | 0-0 | 28-21-22 | D40330J | S/R | | | GD02609 | ST.. | E | *3 | 115-199 |
| 2519B | 20 | GF | BK | | 16-3 | SPARE | D40330J | 25 | | | D40326J | 25 | | | 115-199 |
| 2519R | 20 | GF | BK | | 0-0 | SPARE | D40330J | 24 | | | D40326J | 24 | | | 115-199 |
| 2519Z | | | BK | | 0-0 | SPARE | D40330J | S/R | | | GD02609 | ST.. | E | *3 | 115-199 |
| 2520B | 20 | 2Z | BL | | 16-2 | 23-41-12 | D40330J | 2 | | | SM00002 | | 9 | | ALL |
| 2520R | 20 | 2Z | BL | | 0-0 | 23-41-12 | D40330J | 1 | | | SM00001 | | 9 | | ALL |
| 2520Z | | | BL | | 0-0 | 23-41-12 | D40330J | 4 | | | SM00003 | | 9 | | ALL |
| 2520ZO | | | BL | | 0-0 | 23-41-12 | D40330J | S/R | | | GD00443 | ST.. | E | *1 | ALL |
| 2522B | 20 | GF | AQ | | 16-3 | 28-21-22 | D40330J | 38 | | | D40326J | 38 | | | 001-099 |
| 2522R | 20 | GF | AQ | | 0-0 | 28-21-22 | D40330J | 42 | | | D40326J | 42 | | | 001-099 |
| 2522Z | | | AQ | | 0-0 | 28-21-22 | D40330J | S/R | | | D40326J | | | AD | 001-099 |
| 3501B | 20 | GG | BP | | 16-1 | 28-21-22 | D40328J | 12 | | | D40324J | 12 | | | ALL |
| 3501R | 20 | GG | BP | | 0-0 | 28-21-22 | D40328J | 13 | | | D40324J | 13 | | | ALL |
| 3501Y | 20 | GG | BP | | 0-0 | 28-21-22 | D40328J | 14 | | | D40324J | 14 | | | ALL |
| 3501Z | | | BP | | 0-0 | 28-21-22 | D40328J | S/R | | | GD00433 | ST.. | E | *2 | ALL |
| 3504B | 20 | GG | AV | | 16-3 | 28-21-22 | D40330J | 41 | | | D40326J | 41 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3420

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3426 | 286N3426 | | | VAPOR BARRIER TO WING TIP-RIGHT (continued) | | | | | | | | | | | |
| 3504R | 20 | GG | AV | | 0-0 | 28-21-22 | D40330J | 39 | | | D40326J | 39 | | | 001-099 |
| 3504Y | 20 | GG | AV | | 0-0 | 28-21-22 | D40330J | 40 | | | D40326J | 40 | | | 001-099 |
| 3504Z | | | AV | | 0-0 | 28-21-22 | D40330J | S/R | | | D40326J | | | AD | 001-099 |
| 4251B | 20 | GH | AM | | 47-3 | 27-51-41 | D01805 | 4 | | | D40404J | 5 | | | ALL |
| 4251G | 20 | GH | AM | | 0-0 | 27-51-41 | D01805 | 6 | | | D40404J | 7 | | | ALL |
| 4251R | 20 | GH | AM | | 0-0 | 27-51-41 | D01805 | 3 | | | D40404J | 4 | | | ALL |
| 4251Y | 20 | GH | AM | | 0-0 | 27-51-41 | D01805 | 5 | | | D40404J | 6 | | | ALL |
| 4251Z | | | AM | | 0-0 | 27-51-41 | GD01335 | ST.. | E | * | D40404J | S/R | | | ALL |
| 4252B | 20 | GH | AP | | 47-8 | 27-51-61 | D01805 | 9 | | | D41396J | 4 | | | ALL |
| 4252G | 20 | GH | AP | | 0-0 | 27-51-61 | D01805 | 12 | | | D41396J | 7 | | | ALL |
| 4252R | 20 | GH | AP | | 0-0 | 27-51-61 | D01805 | 10 | | | D41396J | 5 | | | ALL |
| 4252Y | 20 | GH | AP | | 0-0 | 27-51-61 | D01805 | 11 | | | D41396J | 6 | | | ALL |
| 4252Z | | | AP | | 0-0 | 27-51-61 | GD01335 | ST.. | E | * | D41396J | S/R | | | ALL |
| 4253B | 20 | GH | BM | | 16-3 | 28-21-22 | D40330J | 39 | | | D40326J | 39 | | | 115-199 |
| 4253G | 20 | GH | BM | | 0-0 | 28-21-22 | D40330J | 41 | | | D40326J | 41 | | | 115-199 |
| 4253R | 20 | GH | BM | | 0-0 | SPARE | D40330J | 38 | | | D40326J | CAP | Y | | 115-199 |
| 4253Y | 20 | GH | BM | | 0-0 | 28-21-22 | D40330J | 40 | | | D40326J | 40 | | | 115-199 |
| 4253Z | | | BM | | 0-0 | 28-21-22 | D40330J | S/R | | | GD00443 | ST.. | E | *3 | 115-199 |
| 4254B | 20 | GH | AU | | 16-3 | 28-21-23 | D40330J | 44 | | | D40326J | 44 | | | ALL |
| 4254G | 20 | GH | AU | | 0-0 | 28-21-23 | D40330J | 45 | | | D40326J | 45 | | | ALL |
| 4254R | 20 | GH | AU | | 0-0 | 28-21-23 | D40330J | 46 | | | D40326J | 46 | | | ALL |
| 4254Y | 20 | GH | AU | | 0-0 | 28-21-23 | D40330J | 47 | | | D40326J | 47 | | | ALL |
| 4254Z | | | AU | | 0-0 | 28-21-23 | D40330J | S/R | | | GD00443 | ST.. | E | *4 | ALL |
| 4255B | 20 | GH | BR | | 16-1 | 28-21-22 | D40328J | 7 | | | D40324J | 7 | | | ALL |
| 4255G | 20 | GH | BR | | 0-0 | 28-21-22 | D40328J | 8 | | | D40324J | 8 | | | ALL |
| 4255R | 20 | GH | BR | | 0-0 | 28-21-22 | D40328J | 9 | | | D40324J | 9 | | | ALL |
| 4255Y | 20 | GH | BR | | 0-0 | 28-21-22 | D40328J | 20 | | | D40324J | 20 | | | ALL |
| 4255Z | | | BR | | 0-0 | 28-21-22 | D40328J | S/R | | | GD00433 | ST.. | E | *3 | ALL |
| 4256B | 20 | GH | AH | | 16-1 | 28-21-22 | D40328J | 23 | | | D40324J | 23 | | | ALL |
| 4256G | 20 | GH | AH | | 0-0 | 28-21-22 | D40328J | 10 | | | D40324J | 10 | | | ALL |
| 4256R | 20 | GH | AH | | 0-0 | 28-21-22 | D40328J | 11 | | | D40324J | 11 | | | ALL |
| 4256Y | 20 | GH | AH | | 0-0 | 28-21-22 | D40328J | 22 | | | D40324J | 22 | | | ALL |
| 4256Z | | | AH | | 0-0 | 28-21-22 | D40328J | S/R | | | GD00433 | ST.. | E | *3 | ALL |
| A-A | | | | | 0-0 | 33-44-21 | L00021 | J3 | | | M00589 | J2 | | | ALL |
| A-AA | | | | | 0-0 | 23-41-12 | SM00001 | | 9 | | D00417 | RED | | | ALL |
| A-AB | | | | | 0-0 | 23-41-12 | SM00002 | | 9 | | D00417 | BLU | | | ALL |
| A-AC | | | | | 0-0 | 23-41-12 | SM00003 | | 9 | | D00417 | BLK | | | ALL |
| A-AD | | | | | 0-0 | 28-21-11 | SP00580 | | 9 | | L00243 | WHT | | | ALL |
| A-AE | | | | | 0-0 | 28-21-11 | SP00580 | | 9 | | L00379 | WHT | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3420

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3426 | 286N3426 | | | VAPOR BARRIER TO WING TIP-RIGHT (continued) | | | | | | | | | | | |
| A-AF | | | | | 0-0 | 28-21-11 | SP00578 | | | 9 | L00243 | BLK | | | ALL |
| A-AG | | | | | 0-0 | 28-21-11 | SP00578 | | | 9 | L00379 | BLK | | | ALL |
| A-AH | | | | | 0-0 | 28-21-11 | GD00440 | DC.. | E | | S00346 | BLU | | | ALL |
| A-AI | | | | | 0-0 | 28-21-11 | SP00576 | | | 9 | S00346 | RED | | | ALL |
| A-B | | | | | 0-0 | 27-81-31 | S10339 | | 3 | | SP01116 | CAP | Y | | ALL |
| A-C | | | | | 0-0 | 27-81-31 | S10339 | | 1 | | GD01829 | DC.. | E | | ALL |
| A-D | | | | | 0-0 | 27-81-31 | S10339 | | 2 | | SP01116 | | 9 | | ALL |
| FRAA | | | | | 0-0 | 28-41-11 | D40326J | | | AA | D40326J | | 12 | | ALL |
| FRAB | | | | | 0-0 | 28-41-11 | D40326J | | | AA | GD02609 | ST.. | E | | 001-099 |
| FRAB | | | | | 0-0 | 28-41-11 | D40326J | | | AA | GD02609 | ST.. | E | *5 | 115-199 |
| FRAC | | | | | 0-0 | 28-21-11 | GD00433 | ST.. | E | | SP00576 | REF | | AC | 001-099 |
| FRAC | | | | | 0-0 | 28-21-11 | GD00433 | ST.. | E | *4 | SP00576 | REF | | AC | 115-199 |
| FRAD | | | | | 0-0 | 28-21-22 | D40326J | | | AD | GD00443 | ST.. | E | *3 | 001-099 |
| FRAE | | | | | 0-0 | 28-41-11 | D40326J | | | BB | D40326J | | 17 | | ALL |
| FRAF | | | | | 0-0 | 28-41-11 | D40326J | | | BB | GD02609 | ST.. | E | | 001-099 |
| FRAF | | | | | 0-0 | 28-41-11 | D40326J | | | BB | GD02609 | ST.. | E | *5 | 115-199 |
| W3428 | 286N3428 | | | R. WING/BODY DISC TO R. STRUT | | | | | | | | | | | |
| 0001 | 20 | | HL | | 24-5 | 26-11-22 | D40046P | | 5 | | D40048P | | 5 | | ALL |
| 0002 | 20 | | HL | | 24-5 | 26-11-22 | D40046P | | 2 | | D40048P | | 2 | | ALL |
| 0003 | 18 | | HL | | 24-4 | 26-12-21 | D40046P | | 3 | | S10200 | =1 | C | * | ALL |
| 0004 | 18 | | HL | | 4-1 | 26-12-21 | S10200 | | =1 | C | S10201 | =1 | C | * | ALL |
| 0005 | 18 | | HL | | 1-1 | 26-12-21 | S10200 | | =2 | C | GD00232 | DC.. | E | | ALL |
| 0006 | 18 | | HL | | 8-9 | 26-12-21 | S10201 | | =1 | C | D40048P | | 3 | | ALL |
| 0007 | 18 | | HL | | 7-4 | 26-12-21 | S10201 | | =2 | C | GD00249 | DC.. | E | | ALL |
| 0008 | 18 | | HL | | 24-5 | 26-12-21 | D40046P | | 4 | | D40048P | | 4 | | ALL |
| 0009 | 20 | | HL | | 24-5 | SPARE | D40046P | | 1 | | D40048P | | 1 | | ALL |
| 0010 | 20 | | HL | | 24-5 | SPARE | D40046P | | 6 | | D40048P | | 6 | | ALL |
| 0011 | 20 | | HL | | 24-5 | SPARE | D40046P | | 7 | | D40048P | | 7 | | ALL |
| 0012 | 20 | | HL | | 24-5 | 36-11-21 | D40048P | | 8 | | D41210P | | 1 | | ALL |
| 0013 | 20 | | HL | | 24-5 | 36-11-21 | D40048P | | 9 | | D41210P | | 2 | | ALL |
| 0014 | 20 | | HL | | 24-5 | 36-11-21 | D40048P | | 10 | | D41210P | | 3 | | ALL |
| 0015 | 20 | | HL | | 24-5 | 36-11-22 | D40048P | | 11 | | D41210P | | 4 | | ALL |
| 0016 | 20 | | HL | | 24-5 | 36-11-22 | D40048P | | 12 | | D41210P | | 5 | | ALL |
| 0017 | 20 | | HL | | 24-5 | 36-11-22 | D40048P | | 13 | | D41210P | | 13 | | ALL |
| 0018 | 20 | | HL | | 24-5 | 36-11-22 | D40048P | | 14 | | D41210P | | 7 | | ALL |
| 0019 | 18 | | HL | | 1-6 | 36-22-21 | GD02333 | DC.. | E | | SM00001 | | 9 | | ALL |
| 0020 | 20 | | HL | | 1-3 | 36-22-21 | D04662 | | B | | SM00001 | | 9 | | ALL |
| 2001B | 20 | | HM | AA | 25-7 | 36-22-21 | D04662 | | A | | D41210P | | 6 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3420

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3428 | 286N3428 | | | R. WING/BODY DISC TO R. STRUT (continued) | | | | | | | | | | | |
| 2001R | 20 | | HM | AA | 0-0 | 36-22-21 | SM00001 | | | 9 | D41210P | 14 | | | ALL |
| YAAA | | | | | 0-0 | 26-12-21 | D40046P | | S/R | | GD03074 | ST.. | E | *1 | ALL |
| YAAB | | | | | 0-0 | 36-11-21 | D41210P | | S/R | | GD03074 | ST.. | E | *1 | ALL |

WIRE LIST
D280N032

91-21-11
Section W3420
Page 8 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number GA CO TY | | | Fam | Description FT-IN Diagram | | | From Equip Term Type Splice | | | | To Equip Term Type Splice | | | | Effectivity |
|------------------------|-------------------------|--|----|-----|------------------------------------|----------|---------|--------------------------------|----|---|--|------------------------------|------|---|---|-------------|
| | | | | | | | | | | | | | | | | |
| W3430 | 286N3430 | | | | R. STRUT TO BLEED AIR VALVE | | | | | | | | | | | |
| 0001 | 18 | | 7A | | 2-4 | 26-12-21 | D40048J | | 3 | | | S10202 | =1 | L | * | ALL |
| 0002 | 18 | | 7A | | 2-4 | 26-12-21 | D40048J | | 4 | | | S10202 | =1 | L | * | ALL |
| 0003 | 18 | | 7A | | 2-0 | 26-12-21 | S10202 | | =2 | L | | GD00234 | DC.. | N | | ALL |
| 0004 | 20 | | 7A | | 4-3 | 26-11-22 | D40048J | | 5 | | | D40818J | 5 | | | ALL |
| 0005 | 20 | | 7A | | 4-3 | 26-11-22 | D40048J | | 2 | | | D40818J | 2 | | | ALL |
| 0006 | 18 | | 7A | | 2-5 | 36-11-21 | D40048J | | 8 | | | D00554 | 7 | | | ALL |
| 0007 | 18 | | 7A | | 2-5 | 36-11-21 | D40048J | | 9 | | | D00554 | 5 | | | ALL |
| 0008 | 18 | | 7A | | 2-5 | 36-11-21 | D40048J | | 10 | | | D00554 | 2 | | | ALL |
| 0009 | 18 | | 7A | | 1-2 | 36-11-21 | D00554 | | 1 | | | GD01570 | DC.. | N | | ALL |
| 0010 | 18 | | 7A | | 1-2 | 36-11-21 | D00554 | | 3 | | | GD01570 | DC.. | N | | ALL |
| 0011 | 20 | | 7A | | 4-3 | 36-11-22 | D40048J | | 11 | | | D40818J | 3 | | | ALL |
| 0012 | 20 | | 7A | | 4-3 | 36-11-22 | D40048J | | 12 | | | D40818J | 4 | | | ALL |
| 0013 | 20 | | 7A | | 4-3 | 36-11-22 | D40048J | | 13 | | | D40818J | 1 | | | ALL |
| 0014 | 20 | | 7A | | 4-3 | 36-11-22 | D40048J | | 14 | | | D40818J | 6 | | | ALL |
| 0015 | 20 | | 7A | | 4-3 | SPARE | D40048J | | 7 | | | D40818J | 7 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3430

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|---------|------|-------------|--------|-----|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W3446 | 286N3446 | | | | WING BODY TO VAPOR BARRIER-RIGHT AND R. FWD FUEL BOOST PUMP | | | | | | | | | | | |
| 0001 | 20 | | GA | | 25-8 | SPARE | | D42076P | | | | D40404P | 1 | | | ALL |
| 0002 | 18 | | GA | | 2-1 | 28-22-11 | | D01834 | | | | GD01652 | ST.. | E | | ALL |
| 0011 | 20 | | GA | | 25-8 | SPARE | | D42076P | | | | D40404P | 11 | | | ALL |
| 0012 | 20 | | GA | | 25-8 | SPARE | | D42076P | | | | D40404P | 12 | | | ALL |
| 0013 | 20 | | GA | | 25-8 | SPARE | | D42076P | | | | D40404P | 13 | | | ALL |
| 0014 | 20 | | GA | | 25-8 | SPARE | | D42076P | | | | D40404P | 14 | | | ALL |
| 2001B | 20 | | GB | AA | 25-8 | 27-51-41 | | D42076P | | | | D40404P | 3 | | | ALL |
| 2001R | 20 | | GB | AA | 0-0 | 27-51-41 | | D42076P | | | | D40404P | 2 | | | ALL |
| 3001B | 18 | | GC | AC | 11-8 | 28-22-11 | | D42076P | | | | D01834 | 3 | | | ALL |
| 3001R | 18 | | GC | AC | 0-0 | 28-22-11 | | D42076P | | | | D01834 | 1 | | | ALL |
| 3001Y | 18 | | GC | AC | 0-0 | 28-22-11 | | D42076P | | | | D01834 | 2 | | | ALL |
| 4001B | 20 | | GD | AB | 25-8 | 27-51-41 | | D42076P | | | | D40404P | 5 | | | ALL |
| 4001G | 20 | | GD | AB | 0-0 | 27-51-41 | | D42076P | | | | D40404P | 7 | | | ALL |
| 4001R | 20 | | GD | AB | 0-0 | 27-51-41 | | D42076P | | | | D40404P | 4 | | | ALL |
| 4001Y | 20 | | GD | AB | 0-0 | 27-51-41 | | D42076P | | | | D40404P | 6 | | | ALL |
| YAAA | | | | | 0-0 | 27-51-42 | | GD03090 | ST.. | E | | D42076P | S/R | | | ALL |
| W3448 | 286N3448 | | | | WING TIP POSITION LIGHTS-RIGHT | | | | | | | | | | | |
| 0001 | 12 | | GA | | 2-0 | 33-43-12 | | D07086 | | | | GD01328 | ST.. | E | | ALL |
| 0005 | 12 | | GA | | 2-0 | 33-43-12 | | D07086 | | | | SM00002 | | | 9 | ALL |
| 2001B | 12 | | GB | AA | 4-0 | 33-43-12 | | D00028 | | | | SM00002 | | | 9 | ALL |
| 2001R | 12 | | GB | AA | 0-0 | 33-43-12 | | D00028 | | | | SP02872 | | | 9 | ALL |
| 2002B | 12 | | GB | AB | 4-0 | 33-43-12 | | D00028 | | | | SM00004 | | | 9 | ALL |
| 2002R | 12 | | GB | AB | 0-0 | 33-43-12 | | D00028 | | | | SM00006 | | | 9 | ALL |
| 2003B | 12 | | GB | AC | 7-0 | 33-43-12 | | D00030 | | | | SM00002 | | | 9 | ALL |
| 2003R | 12 | | GB | AC | 0-0 | 33-43-12 | | D00030 | | | | SP02872 | | | 9 | ALL |
| 2004B | 12 | | GB | AD | 7-0 | 33-43-12 | | D00030 | | | | SM00004 | | | 9 | ALL |
| 2004R | 12 | | GB | AD | 0-0 | 33-43-12 | | D00030 | | | | SM00006 | | | 9 | ALL |
| 2005B | 12 | | GB | AF | 2-0 | 33-43-12 | | D07086 | | | | SP02874 | | | 9 | ALL |
| 2005R | 12 | | GB | AF | 0-0 | 33-43-12 | | D07086 | | | | SP02872 | | | 9 | ALL |
| 2006B | 12 | | GB | AG | 2-0 | 33-43-12 | | D07086 | | | | SM00004 | | | 9 | ALL |
| 2006R | 12 | | GB | AG | 0-0 | 33-43-12 | | D07086 | | | | SM00006 | | | 9 | ALL |

WIRE LIST

D280N032

91-21-11

Section W3440

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3458 | 286N3458 | | | R. WING/BODY DISC TO VAPOR SEAL DISC (FUELING PNL WIRING) | | | | | | | | | | | |
| 0002 | 20 | | GA | | 26-3 | 28-26-11 | D40332P | | 2 | | D40328P | | 2 | | ALL |
| 0003 | 20 | | GA | | 26-3 | 28-26-11 | D40332P | | 3 | | D40328P | | 3 | | ALL |
| 0004 | 20 | | GA | | 26-3 | 28-26-11 | D40332P | | 4 | | D40328P | | 4 | | ALL |
| 0005 | 20 | | GA | | 26-3 | 28-26-11 | D40332P | | 5 | | D40328P | | 5 | | ALL |
| 0006 | 20 | | GA | | 26-3 | 28-26-11 | D40332P | | 6 | | D40328P | | 6 | | ALL |
| 0007 | 20 | | GA | | 26-3 | 28-21-22 | D40332P | | 7 | | D40328P | | 7 | | ALL |
| 0008 | 20 | | GA | | 26-3 | 28-21-22 | D40332P | | 8 | | D40328P | | 8 | | ALL |
| 0009 | 20 | | GA | | 26-3 | 28-21-22 | D40332P | | 9 | | D40328P | | 9 | | ALL |
| 0015 | 20 | | GA | | 26-3 | 28-21-21 | D40332P | | 15 | | D40328P | | 15 | | ALL |
| 0016 | 20 | | GA | | 26-3 | 28-21-21 | D40332P | | 16 | | D40328P | | 16 | | ALL |
| 0017 | 20 | | GA | | 26-3 | 28-21-11 | D40332P | | 17 | | D40328P | | 17 | | ALL |
| 0020 | 20 | | GA | | 26-3 | 28-21-22 | D40332P | | 20 | | D40328P | | 20 | | ALL |
| 2001B | 20 | | GB | AA | 26-3 | SPARE | D40332P | | 18 | | D40328P | | 18 | | ALL |
| 2001R | 20 | | GB | AA | 0-0 | SPARE | D40332P | | 19 | | D40328P | | 19 | | ALL |
| 3001B | 20 | | GC | AD | 26-3 | 28-21-22 | D40332P | | 12 | | D40328P | | 12 | | ALL |
| 3001R | 20 | | GC | AD | 0-0 | 28-21-22 | D40332P | | 13 | | D40328P | | 13 | | ALL |
| 3001Y | 20 | | GC | AD | 0-0 | 28-21-22 | D40332P | | 14 | | D40328P | | 14 | | ALL |
| 4001B | 20 | | GD | AE | 26-3 | 28-21-22 | D40332P | | 23 | | D40328P | | 23 | | ALL |
| 4001G | 20 | | GD | AE | 0-0 | 28-21-22 | D40332P | | 10 | | D40328P | | 10 | | ALL |
| 4001R | 20 | | GD | AE | 0-0 | 28-21-22 | D40332P | | 11 | | D40328P | | 11 | | ALL |
| 4001Y | 20 | | GD | AE | 0-0 | 28-21-22 | D40332P | | 22 | | D40328P | | 22 | | 001-099 |
| 4001Y | 20 | | GD | AE | 0-0 | 28-21-22 | D40332P | | 21 | | D40328P | | 22 | | 115-199 |
| YAAA | | | | | 0-0 | 28-21-11 | GD03092 | ST.. | E | | D40332P | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3450

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3460 | 286N3460 | | | R. WING/BODY DISC. TO VAPOR SEAL DISC. (FUELING PANEL) | | | | | | | | | | | |
| 0001 | 20 | | GA | | 25-11 | 28-21-23 | D40334P | | 47 | | D40330P | | 47 | | ALL |
| 0002 | 20 | | GA | | 25-11 | 28-21-23 | D40334P | | 46 | | D40330P | | 46 | | ALL |
| 0003 | 20 | | GA | | 25-11 | 28-21-23 | D40334P | | 45 | | D40330P | | 45 | | ALL |
| 0004 | 20 | | GA | | 25-11 | 28-21-23 | D40334P | | 44 | | D40330P | | 44 | | ALL |
| 0005 | 20 | | GA | | 25-11 | 28-21-11 | D40334P | | 5 | | D40330P | | 5 | | ALL |
| 0006 | 20 | | GA | | 25-11 | 28-21-11 | D40334P | | 6 | | D40330P | | 6 | | ALL |
| 0007 | 20 | | GA | | 25-11 | 28-21-11 | D40334P | | 7 | | D40330P | | 7 | | ALL |
| 0009 | 20 | | GA | | 25-11 | 28-41-11 | D40334P | | 9 | | D40330P | | 9 | | 115-199 |
| 0014 | 20 | | GA | | 25-11 | 28-41-11 | D40334P | | 14 | | D40330P | | 14 | | ALL |
| 0015 | 20 | | GA | | 25-11 | SPARE | D40334P | | 15 | | D40330P | | 15 | | 115-199 |
| 0020 | 20 | | GA | | 25-11 | 28-41-11 | D40334P | | 20 | | D40330P | | 20 | | ALL |
| 0021 | 20 | | GA | | 25-11 | SPARE | D40334P | | 21 | | D40330P | | 21 | | 115-199 |
| 2001B | 20 | | GB | AB | 25-11 | SPARE | D40334P | | 48 | | D40330P | | 48 | | ALL |
| 2001R | 20 | | GB | AB | 0-0 | SPARE | D40334P | | 49 | | D40330P | | 49 | | ALL |
| 2002B | 20 | | GB | AC | 25-11 | SPARE | D40334P | | 50 | | D40330P | | 50 | | ALL |
| 2002R | 20 | | GB | AC | 0-0 | SPARE | D40334P | | 51 | | D40330P | | 51 | | ALL |
| 2003B | 20 | | GB | AD | 25-11 | SPARE | D40334P | | 52 | | D40330P | | 52 | | ALL |
| 2003R | 20 | | GB | AD | 0-0 | SPARE | D40334P | | 53 | | D40330P | | 53 | | ALL |
| 2004B | 20 | | GB | AE | 25-11 | SPARE | D40334P | | 54 | | D40330P | | 54 | | ALL |
| 2004R | 20 | | GB | AE | 0-0 | SPARE | D40334P | | 55 | | D40330P | | 55 | | ALL |
| 2006B | 20 | | GB | AH | 25-11 | SPARE | D40334P | | CAP | Y | D40330P | | CAP | Y | 115-199 |
| 2006R | 20 | | GB | AH | 0-0 | SPARE | D40334P | | CAP | Y | D40330P | | CAP | Y | 115-199 |
| 2007B | 20 | | GB | AI | 25-11 | SPARE | D40334P | | 13 | | D40330P | | 13 | | 115-199 |
| 2007R | 20 | | GB | AI | 0-0 | SPARE | D40334P | | CAP | Y | D40330P | | 12 | | 115-199 |
| 2009B | 20 | | GB | AK | 25-11 | SPARE | D40334P | | CAP | Y | D40330P | | 17 | | 115-199 |
| 2009R | 20 | | GB | AK | 0-0 | SPARE | D40334P | | 16 | | D40330P | | 16 | | 115-199 |
| 2010B | 20 | | GB | AL | 25-11 | SPARE | D40334P | | CAP | Y | D40330P | | CAP | Y | 115-199 |
| 2010R | 20 | | GB | AL | 0-0 | SPARE | D40334P | | CAP | Y | D40330P | | CAP | Y | 115-199 |
| 2012B | 20 | | GB | AN | 25-11 | 28-21-22 | D40334P | | 23 | | D40330P | | 23 | | 115-199 |
| 2012R | 20 | | GB | AN | 0-0 | 28-21-22 | D40334P | | 22 | | D40330P | | 22 | | 115-199 |
| 2013B | 20 | | GB | AO | 25-11 | SPARE | D40334P | | 25 | | D40330P | | 25 | | 115-199 |
| 2013R | 20 | | GB | AO | 0-0 | SPARE | D40334P | | 24 | | D40330P | | 24 | | 115-199 |
| 2014B | 20 | | GB | AF | 25-11 | 28-21-22 | D40334P | | 38 | | D40330P | | 38 | | 001-099 |
| 2014R | 20 | | GB | AF | 0-0 | 28-21-22 | D40334P | | 42 | | D40330P | | 42 | | 001-099 |
| 2501B | 20 | | GF | AA | 25-11 | 23-41-12 | D40334P | | 2 | | D40330P | | 2 | | 001-099 |
| 2501R | 20 | | GF | AA | 0-0 | 23-41-12 | D40334P | | 1 | | D40330P | | 1 | | 001-099 |
| 2501Z | | | | AA | 0-0 | 23-41-12 | D40334P | | 4 | | D40330P | | 4 | | 001-099 |
| 2506B | 20 | | GF | AH | 25-11 | 28-41-11 | D40334P | | 11 | | D40330P | | 11 | | 001-099 |
| 2506B | 20 | | GF | HA | 26-0 | 28-41-11 | D40334P | | 11 | | D40330P | | 11 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3460

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3460 | 286N3460 | | | R. WING/BODY DISC. TO VAPOR SEAL DISC. (FUELING PANEL) (continued) | | | | | | | | | | | |
| 2506R | 20 | GF | AH | | 0-0 | 28-41-11 | D40334P | 10 | | | D40330P | 10 | | | 001-099 |
| 2506R | 20 | GF | HA | | 0-0 | 28-41-11 | D40334P | 10 | | | D40330P | 10 | | | 115-199 |
| 2506Z | | | AH | | 0-0 | 28-41-11 | D40334P | 12 | | | D40330P | S/R | | | 001-099 |
| 2506Z | | | HA | | 0-0 | 28-41-11 | D40334P | 12 | | | D40330P | S/R | | | 115-199 |
| 2510B | 20 | GF | AL | | 25-11 | 28-41-11 | D40334P | 19 | | | D40330P | 19 | | | 001-099 |
| 2510B | 20 | GF | LA | | 26-0 | 28-41-11 | D40334P | 19 | | | D40330P | 19 | | | 115-199 |
| 2510R | 20 | GF | AL | | 0-0 | 28-41-11 | D40334P | 18 | | | D40330P | 18 | | | 001-099 |
| 2510R | 20 | GF | LA | | 0-0 | 28-41-11 | D40334P | 18 | | | D40330P | 18 | | | 115-199 |
| 2510Z | | | AL | | 0-0 | 28-41-11 | D40334P | 17 | | | D40330P | S/R | | | 001-099 |
| 2510Z | | | LA | | 0-0 | 28-41-11 | D40334P | 17 | | | D40330P | S/R | | | 115-199 |
| 3001B | 20 | GC | AG | | 25-11 | 28-21-22 | D40334P | 41 | | | D40330P | 41 | | | 001-099 |
| 3001R | 20 | GC | AG | | 0-0 | 28-21-22 | D40334P | 39 | | | D40330P | 39 | | | 001-099 |
| 3001Y | 20 | GC | AG | | 0-0 | 28-21-22 | D40334P | 40 | | | D40330P | 40 | | | 001-099 |
| 3501B | 20 | GG | AA | | 25-11 | 23-41-12 | D40334P | 2 | | | D40330P | 2 | | | 115-199 |
| 3501R | 20 | GG | AA | | 0-0 | 23-41-12 | D40334P | 1 | | | D40330P | 1 | | | 115-199 |
| 3501Y | 20 | GG | AA | | 0-0 | 23-41-12 | D40334P | 3 | | | D40330P | 3 | | | 115-199 |
| 3501Z | | | AA | | 0-0 | 23-41-12 | D40334P | 4 | | | D40330P | 4 | | | 115-199 |
| 4001B | 20 | GD | AP | | 25-11 | 28-21-22 | D40334P | 39 | | | D40330P | 39 | | | 115-199 |
| 4001G | 20 | GD | AP | | 0-0 | 28-21-22 | D40334P | 41 | | | D40330P | 41 | | | 115-199 |
| 4001R | 20 | GD | AP | | 0-0 | SPARE | D40334P | 38 | | | D40330P | 38 | | | 115-199 |
| 4001Y | 20 | GD | AP | | 0-0 | 28-21-22 | D40334P | 40 | | | D40330P | 40 | | | 115-199 |
| YAAA | | | | | 0-0 | 28-21-11 | GD03092 | ST.. | E | | D40334P | S/R | | | ALL |
| W3462 | 286N3462 | | | VAPOR BARRIER TO FUEL QTY SENSOR(LO-Z). | | | | | | | | | | | |
| 4501AA | 20 | 4K | AT | | 1-0 | SPARE | D02814 | 13 | | | D41196J | 14 | | | 115-199 |
| 4501RB | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 4 | | | D41196J | 5 | | | 115-199 |
| 4501RG | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 3 | | | D41196J | 4 | | | 115-199 |
| 4501RK | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 2 | | | D41196J | 3 | | | 115-199 |
| 4501RV | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 6 | | | D41196J | 7 | | | 115-199 |
| 4501RY | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 1 | | | D41196J | 2 | | | 115-199 |
| 4501W | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 16 | | | D41196J | 1 | | | 115-199 |
| 4501WB | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 12 | | | D41196J | 13 | | | 115-199 |
| 4501WG | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 11 | | | D41196J | 12 | | | 115-199 |
| 4501WK | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 5 | | | D41196J | 6 | | | 115-199 |
| 4501WN | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 7 | | | D41196J | 8 | | | 115-199 |
| 4501WO | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 10 | | | D41196J | 11 | | | 115-199 |
| 4501WR | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 8 | | | D41196J | 9 | | | 115-199 |
| 4501WV | 20 | 4K | AT | | 0-0 | SPARE | D02814 | 14 | | | D41196J | 15 | | | 115-199 |
| 4501WY | 20 | 4K | AT | | 0-0 | 28-41-31 | D02814 | 9 | | | D41196J | 10 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3460

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3462 | 286N3462 | | | VAPOR BARRIER TO FUEL QTY SENSOR(LO-Z). (continued) | | | | | | | | | | | |
| 4501Z | | | | AT | 0-0 | 28-41-31 | GD01959 | ST.. | E | | D41196J | S/R | | | 115-199 |
| W3466 | 286N3466 | | | LWR R. STRUT TO BLEED AIR VLAVE | | | | | | | | | | | |
| 0001 | 18 | | 7A | | 3-4 | 26-11-22 | D40818P | | 5 | | D02800 | A | | | ALL |
| 0002 | 18 | | 7A | | 3-4 | 26-11-22 | D40818P | | 2 | | D02800 | D | | | ALL |
| 0003 | 20 | | 7A | | 2-5 | 36-11-22 | D40818P | | 3 | | D02690 | 6 | | | ALL |
| 0004 | 20 | | 7A | | 2-5 | 36-11-22 | D40818P | | 4 | | D02690 | 1 | | | ALL |
| 0005 | 20 | | 7A | | 2-5 | 36-11-22 | D40818P | | 1 | | D02690 | 8 | | | ALL |
| 0006 | 20 | | 7A | | 2-5 | 36-11-22 | D40818P | | 6 | | D02690 | 3 | | | ALL |
| 0007 | 18 | | 7A | | 1-8 | 36-11-22 | D02690 | | 5 | | GD01578 | DC.. | N | | ALL |
| 0008 | 18 | | 7A | | 1-8 | 36-11-22 | D02690 | | 10 | | GD01578 | DC.. | N | | ALL |
| 0009 | 18 | | 7A | | 1-8 | 36-11-22 | D02690 | | 9 | | GD01578 | DC.. | N | | ALL |
| W3468 | 286N3468 | | | RIGHT FIREWALLDISC. TO NACELLE OVHT DETECTORS | | | | | | | | | | | |
| 0001 | 18 | | 7A | | 3-0 | 26-11-22 | D41074P | | 5 | | D02804 | A | | | ALL |
| 0002 | 18 | | 7A | | 3-0 | 26-11-22 | D41074P | | 2 | | D02804 | D | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3460

Page 3 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|-----|
| | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3470 | 286N3470 | | | RIGHT STRUT DISC TO STRUT OVHT SWITCHES | | | | | | | | | | | |
| 0001 | 20 | 7A | | 6-3 | 26-11-22 | D41074J | | 5 | | | D41164J | | 5 | | ALL |
| 0002 | 20 | 7A | | 6-3 | 26-11-22 | D41074J | | 2 | | | D41164J | | 2 | | ALL |
| 0003 | 18 | 7A | | 3-3 | 26-12-21 | D41164J | | 3 | | | S10205 | = 1 | L | * | ALL |
| 0004 | 18 | 7A | | 3-3 | 26-12-21 | D41164J | | 4 | | | S10205 | = 1 | L | * | ALL |
| 0005 | 18 | 7A | | 2-8 | 26-12-21 | S10205 | | = 2 | L | | GD02036 | DC.. | N | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3470

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3480 | 286N3480 | | | | RIGHT ENGINE STRUT TO RIGHT FRONT/SPAR DISC | | | | | | | | | | | |
| 0012 | 20 | | GA | | 21-1 | SPARE | | D42290J | | 16 | | D41358P | | 16 | | ALL |
| 0018R | 20 | | QA | | 21-1 | 26-11-21 | | D42290J | | 25 | | D41358P | | 25 | | ALL |
| 0019R | 20 | | QA | | 21-1 | 26-11-21 | | D42290J | | 33 | | D41358P | | 33 | | ALL |
| 0020R | 20 | | QA | | 21-1 | 26-11-21 | | D42290J | | 27 | | D41358P | | 27 | | ALL |
| 0021 | 18 | | GA | | 21-1 | 26-13-21 | | D42290J | | 28 | | D41358P | | 28 | 18 | ALL |
| 0022 | 18 | | GA | | 21-1 | 26-13-21 | | D42290J | | 34 | | D41358P | | 34 | 18 | ALL |
| 0027 | 20 | | GA | | 21-1 | 78-34-21 | | D41358P | | 32 | | D42290J | | 32 | | ALL |
| 1001 | 20 | | GE | T | 21-1 | 74-31-21 | | D42290J | | 15 | | D41358P | | 15 | | ALL |
| 1001Z | | | | T | 0-0 | 74-31-21 | | D42290J | S/R | | | D41358P | S/R | | | ALL |
| 2501B | 20 | | GF | AA | 21-1 | 77-12-11 | | D42290J | | 5 | | D41358P | | 5 | | ALL |
| 2501R | 20 | | GF | AA | 0-0 | 77-12-11 | | D42290J | | 4 | | D41358P | | 4 | | ALL |
| 2501Z | | | | AA | 0-0 | 77-12-11 | | D42290J | S/R | | | D41358P | S/R | | | ALL |
| 2502B | 20 | | GF | AB | 21-1 | 77-12-21 | | D42290J | | 8 | | D41358P | | 8 | | ALL |
| 2502R | 20 | | GF | AB | 0-0 | 77-12-21 | | D42290J | | 7 | | D41358P | | 7 | | ALL |
| 2502Z | | | | AB | 0-0 | 77-12-21 | | D42290J | S/R | | | D41358P | S/R | | | ALL |
| 2503B | 20 | | GF | AF | 21-1 | 74-31-21 | | D42290J | | 2 | | D41358P | | 2 | | ALL |
| 2503R | 20 | | GF | AF | 0-0 | 74-31-21 | | D42290J | | 3 | | D41358P | | 3 | | ALL |
| 2503Z | | | | AF | 0-0 | 74-31-21 | | D42290J | S/R | | | D41358P | S/R | | | ALL |
| 2504B | 20 | | GF | AG | 21-1 | SPARE | | D42290J | | 17 | | D41358P | | 17 | | ALL |
| 2504R | 20 | | GF | AG | 0-0 | SPARE | | D42290J | | 18 | | D41358P | | 18 | | ALL |
| 2504Z | | | | AG | 0-0 | SPARE | | D42290J | S/R | | | D41358P | S/R | | | ALL |
| 2505B | 20 | | GF | AH | 21-1 | SPARE | | D42290J | | 30 | | D41358P | | 30 | | ALL |
| 2505R | 20 | | GF | AH | 0-0 | SPARE | | D42290J | | 31 | | D41358P | | 31 | | ALL |
| 2505Z | | | | AH | 0-0 | SPARE | | D42290J | S/R | | | D41358P | S/R | | | ALL |
| 2506B | 18 | | GF | AJ | 21-1 | 30-34-22 | | D42290J | | 35 | | D41358P | | 37 | 18 | 001-099 |
| 2506B | 18 | | GF | AK | 21-1 | 30-34-22 | | D42290J | | 35 | | D41358P | | 37 | 18 | 115-199 |
| 2506R | 18 | | GF | AJ | 0-0 | 30-34-22 | | D42290J | | 36 | | D41358P | | 38 | 18 | 001-099 |
| 2506R | 18 | | GF | AK | 0-0 | 30-34-22 | | D42290J | | 36 | | D41358P | | 38 | 18 | 115-199 |
| 2506Z | | | | AJ | 0-0 | 30-34-22 | | D42290J | S/R | | | D41358P | S/R | | | 001-099 |
| 2506Z | | | | AK | 0-0 | 30-34-22 | | D42290J | S/R | | | D41358P | S/R | | | 115-199 |
| 3501B | 20 | | GG | AE | 21-1 | 80-11-21 | | D42290J | | 12 | | D41358P | | 12 | | ALL |
| 3501R | 20 | | GG | AE | 0-0 | 80-11-21 | | D42290J | | 13 | | D41358P | | 13 | | ALL |
| 3501Y | 20 | | GG | AE | 0-0 | 80-11-21 | | D42290J | | 14 | | D41358P | | 14 | | ALL |
| 3501Z | | | | AE | 0-0 | 80-11-21 | | D42290J | S/R | | | D41358P | S/R | | | ALL |
| 4251B | 20 | | GH | AD | 21-1 | 79-35-11 | | D42290J | | 11 | | D41358P | | 11 | | ALL |
| 4251G | 20 | | GH | AD | 0-0 | 79-33-11 | | D42290J | | 10 | | D41358P | | 10 | | ALL |
| 4251R | 20 | | GH | AD | 0-0 | 73-33-11 | | D42290J | | 1 | | D41358P | | 1 | | ALL |
| 4251Y | 20 | | GH | AD | 0-0 | 73-34-11 | | D42290J | | 21 | | D41358P | | 21 | | ALL |
| 4251Z | | | | AD | 0-0 | 79-35-11 | | D42290J | S/R | | | D41358P | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3480

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3480 | 286N3480 | | | RIGHT ENGINE STRUT TO RIGHT FRONT/SPAR DISC (continued) | | | | | | | | | | | |
| 4501G | 20 | DU | AC | | 21-1 | 77-21-11 | D42290J | 22 | 4H | | D41358P | 22 | TC | | ALL |
| 4501W | 20 | DU | AC | | 0-0 | 77-21-11 | D42290J | 23 | 4L | | D41358P | 23 | TD | | ALL |
| 4501Z | | | AC | | 0-0 | 77-21-11 | D42290J | S/R | | | D41358P | S/R | | | ALL |
| YAAA | | | | | 0-0 | 80-11-21 | GD03088 | ST.. | E | | D41358P | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3480

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3501 | 286N3501 | | | PASSENGER ADDRESS MUTED SPKR-DR 4 | | | | | | | | | | | |
| 0001 | 22 | | GA | | 15-0 | 23-31-22 | D01223 | | 3 | | D01221 | | 3 | | 001-099 |
| 0001 | 22 | | GA | | 10-0 | 23-31-22 | D01223 | | 3 | | D01221 | | 3 | | 115-199 |
| 0002 | 22 | | GA | | 15-0 | 23-31-22 | D01223 | | 4 | | D01221 | | 7 | | 001-099 |
| 0002 | 22 | | GA | | 10-0 | 23-31-22 | D01223 | | 4 | | D01221 | | 7 | | 115-199 |
| 2001B | 22 | | GB | AA | 15-0 | 23-31-22 | D01223 | | 1 | | D01221 | | 2 | | 001-099 |
| 2001B | 22 | | GB | AA | 10-0 | 23-31-22 | D01223 | | 1 | | D01221 | | 2 | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 23-31-22 | D01223 | | 2 | | D01221 | | 6 | | ALL |
| 2002B | 22 | | GB | AB | 3-0 | 23-31-22 | D04701P | 1 | VG | * | D01221 | | 4 | | ALL |
| 2002R | 22 | | GB | AB | 0-0 | 23-31-22 | D04703J | 1 | VY | * | D01221 | | 8 | | ALL |
| 2003B | 22 | | GB | AC | 3-0 | 23-31-22 | D04701P | 1 | VG | * | B10110 | COM | AC | | ALL |
| 2003R | 22 | | GB | AC | 0-0 | 23-31-22 | D04703J | 1 | VY | * | B10110 | 1K | AD | | ALL |
| W3503 | 286N3503 | | | ATTENDANTS HANDSET JUMPER DR 2-LEFT TO RIGHT | | | | | | | | | | | |
| 4251B | 24 | | G4 | AA | 23-0 | 23-42-11 | D40065P | | 3 | | D40063J | | 3 | | 115-199 |
| 4251G | 24 | | G4 | AA | 0-0 | 23-42-11 | D40065P | | 5 | | D40063J | | 5 | | 115-199 |
| 4251R | 24 | | G4 | AA | 0-0 | 23-42-11 | D40065P | | 1 | | D40063J | | 1 | | 115-199 |
| 4251Y | 24 | | G4 | AA | 0-0 | 23-42-11 | D40065P | | 4 | | D40063J | | 4 | | 115-199 |
| 4251Z | | | | AA | 0-0 | 23-42-11 | D40065P | | 2 | | D40063J | | 2 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3500

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3514 | 286N3514 | | | | FLUORESCENT LIGHTING-CEILING, LEFT FORWARD | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 12-0 | 33-21-12 | D05348 | | 1 | | | SM00031 | | 9 | | 001-099 | |
| 0002 | 20 | | GA | | 5-0 | 33-21-12 | D05348 | | 2 | | | GD02877 | AC.. | E | | 001-099 | |
| 0003 | 24 | | GK | | 22-0 | 33-21-12 | D05348 | | 3 | | | SM00033 | | 9 | | 001-099 | |
| 0004 | 20 | | GA | | 5-0 | 33-21-12 | D05348 | | 4 | | | GD02879 | ST.. | E | | 001-099 | |
| 0011 | 20 | | GA | | 16-0 | 33-21-12 | D00342 | | 1 | | | SM00011 | | 9 | | 001-099 | |
| 0012 | 20 | | GA | | 6-0 | 33-21-12 | D00342 | | 2 | | | GD00621 | AC.. | E | | 001-099 | |
| 0013 | 24 | | GK | | 16-0 | 33-21-12 | D00342 | | 3 | | | SM00013 | | 9 | | 001-099 | |
| 0014 | 20 | | GA | | 6-0 | 33-21-12 | D00342 | | 4 | | | GD00622 | ST.. | E | | 001-099 | |
| 0015 | 22 | | GA | | 12-0 | 33-21-12 | D00342 | | 5 | | | D00340 | | 5 | | 001-099 | |
| 0016 | 22 | | GA | | 12-0 | 33-21-12 | D00342 | | 6 | | | D00340 | | 6 | | 001-099 | |
| 0017 | 22 | | GA | | 12-0 | 33-21-12 | D00342 | | 7 | | | D00340 | | 7 | | 001-099 | |
| 0018 | 22 | | GA | | 12-0 | 33-21-12 | D00342 | | 8 | | | D00340 | | 8 | | 001-099 | |
| 0019 | 22 | | GA | | 12-0 | 33-21-12 | D00342 | | 9 | | | D00340 | | 9 | | 001-099 | |
| 0020 | 20 | | GA | | 6-0 | 33-21-51 | D00346 | | 10 | | | SM00010 | | 9 | | 001-099 | |
| 0021 | 20 | | GA | | 7-0 | 33-21-12 | D00346 | | 1 | | | SM00011 | | 9 | | 001-099 | |
| 0022 | 20 | | GA | | 4-0 | 33-21-12 | D00346 | | 2 | | | GD00623 | AC.. | E | | 001-099 | |
| 0023 | 24 | | GK | | 7-0 | 33-21-12 | D00346 | | 3 | | | SM00013 | | 9 | | 001-099 | |
| 0024 | 20 | | GA | | 4-0 | 33-21-12 | D00346 | | 4 | | | GD00624 | ST.. | E | | 001-099 | |
| 0025 | 22 | | GA | | 13-0 | 33-21-12 | D00346 | | 5 | | | D00344 | | 5 | | 001-099 | |
| 0026 | 22 | | GA | | 13-0 | 33-21-12 | D00346 | | 6 | | | D00344 | | 6 | | 001-099 | |
| 0027 | 22 | | GA | | 13-0 | 33-21-12 | D00346 | | 7 | | | D00344 | | 7 | | 001-099 | |
| 0028 | 22 | | GA | | 13-0 | 33-21-12 | D00346 | | 8 | | | D00344 | | 8 | | 001-099 | |
| 0029 | 22 | | GA | | 13-0 | 33-21-12 | D00346 | | 9 | | | D00344 | | 9 | | 001-099 | |
| 0031 | 20 | | GA | | 6-0 | 33-21-12 | D00350 | | 1 | | | SM00031 | | 9 | | 001-099 | |
| 0031 | 20 | | GA | | 11-0 | 33-21-12 | D00350 | | 1 | | | SM00131 | | 9 | | 115-199 | |
| 0032 | 20 | | GA | | 4-0 | 33-21-12 | D00350 | | 2 | | | GD00625 | AC.. | E | | 001-099 | |
| 0032 | 20 | | GA | | 6-0 | 33-21-12 | D00350 | | 2 | | | GD00625 | AC.R | E | | 115-199 | |
| 0033 | 24 | | GK | | 15-0 | 33-21-12 | D00350 | | 3 | | | SM00033 | | 9 | | 001-099 | |
| 0033 | 24 | | GK | | 11-0 | 33-21-12 | D00350 | | 3 | | | SM00133 | | 9 | | 115-199 | |
| 0034 | 20 | | GA | | 4-0 | 33-21-12 | D00350 | | 4 | | | GD00626 | ST.. | E | | 001-099 | |
| 0034 | 20 | | GA | | 6-0 | 33-21-12 | D00350 | | 4 | | | GD00626 | ST.R | E | | 115-199 | |
| 0035 | 22 | | GA | | 13-0 | 33-21-12 | D00350 | | 5 | | | D00354 | | 5 | | 001-099 | |
| 0035 | 22 | | GA | | 14-0 | 33-21-12 | D00350 | | 5 | | | D00354 | | 5 | | 115-199 | |
| 0036 | 22 | | GA | | 13-0 | 33-21-12 | D00350 | | 6 | | | D00354 | | 6 | | 001-099 | |
| 0036 | 22 | | GA | | 14-0 | 33-21-12 | D00350 | | 6 | | | D00354 | | 6 | | 115-199 | |
| 0037 | 22 | | GA | | 13-0 | 33-21-12 | D00350 | | 7 | | | D00354 | | 7 | | 001-099 | |
| 0037 | 22 | | GA | | 14-0 | 33-21-12 | D00350 | | 7 | | | D00354 | | 7 | | 115-199 | |
| 0038 | 22 | | GA | | 13-0 | 33-21-12 | D00350 | | 8 | | | D00354 | | 8 | | 001-099 | |
| 0038 | 22 | | GA | | 14-0 | 33-21-12 | D00350 | | 8 | | | D00354 | | 8 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W3510

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3514 | 286N3514 | | | | FLUORESCENT LIGHTING-CEILING, LEFT FORWARD (continued) | | | | | | | | | | | |
| 0039 | 22 | | GA | | 13-0 | 33-21-12 | | D00350 | | | | D00354 | 9 | | | 001-099 |
| 0039 | 22 | | GA | | 14-0 | 33-21-12 | | D00350 | | | | D00354 | 9 | | | 115-199 |
| 0041 | 20 | | GA | | 7-0 | 33-21-12 | | D00356 | | | | SM00041 | | 9 | | 001-099 |
| 0042 | 20 | | GA | | 6-0 | 33-21-12 | | D00356 | | | | GD00627 | AC.. | E | | 001-099 |
| 0043 | 24 | | GK | | 8-0 | 33-21-12 | | D00356 | | | | SM00043 | | 9 | | 001-099 |
| 0044 | 20 | | GA | | 6-0 | 33-21-12 | | D00356 | | | | GD00628 | ST.. | E | | 001-099 |
| 0045 | 22 | | GA | | 14-0 | 33-21-12 | | D00356 | | | | D00358 | 5 | | | 001-099 |
| 0046 | 22 | | GA | | 14-0 | 33-21-12 | | D00356 | | | | D00358 | 6 | | | 001-099 |
| 0047 | 22 | | GA | | 14-0 | 33-21-12 | | D00356 | | | | D00358 | 7 | | | 001-099 |
| 0048 | 22 | | GA | | 14-0 | 33-21-12 | | D00356 | | | | D00358 | 8 | | | 001-099 |
| 0049 | 22 | | GA | | 14-0 | 33-21-12 | | D00356 | | | | D00358 | 9 | | | 001-099 |
| 0061 | 20 | | GA | | 49-0 | 33-21-12 | | D04512 | | | | SM00061 | | 9 | | 115-199 |
| 0062 | 20 | | GA | | 4-0 | 33-21-12 | | D04512 | | | | GD02149 | AC.R | E | | 115-199 |
| 0063 | 24 | | GK | | 49-0 | 33-21-12 | | D04512 | | | | SM00063 | | 9 | | 115-199 |
| 0064 | 20 | | GA | | 4-0 | 33-21-12 | | D04512 | | | | GD02150 | ST.R | E | | 115-199 |
| 0091 | 20 | | GA | | 4-0 | 33-21-12 | | D04594 | | | | SM00091 | | 9 | | 115-199 |
| 0092 | 20 | | GA | | 4-0 | 33-21-12 | | D04594 | | | | GD02153 | AC.R | E | | 115-199 |
| 0093 | 24 | | GK | | 4-0 | 33-21-12 | | D04594 | | | | SM00093 | | 9 | | 115-199 |
| 0094 | 20 | | GA | | 4-0 | 33-21-12 | | D04594 | | | | GD02154 | ST.R | E | | 115-199 |
| 0111 | 20 | | GA | | 10-0 | 33-21-12 | | D00342 | | | | SM00011 | | 9 | | 115-199 |
| 0112 | 20 | | GA | | 5-0 | 33-21-12 | | D00342 | | | | GD00621 | AC.R | E | | 115-199 |
| 0113 | 24 | | GK | | 10-0 | 33-21-12 | | D00342 | | | | SM00013 | | 9 | | 115-199 |
| 0114 | 20 | | GA | | 5-0 | 33-21-12 | | D00342 | | | | GD00622 | ST.R | E | | 115-199 |
| 0115 | 22 | | GA | | 11-0 | 33-21-12 | | D00342 | | | | D00344 | 5 | | | 115-199 |
| 0116 | 22 | | GA | | 11-0 | 33-21-12 | | D00342 | | | | D00344 | 6 | | | 115-199 |
| 0117 | 22 | | GA | | 11-0 | 33-21-12 | | D00342 | | | | D00344 | 7 | | | 115-199 |
| 0118 | 22 | | GA | | 11-0 | 33-21-12 | | D00342 | | | | D00344 | 8 | | | 115-199 |
| 0119 | 22 | | GA | | 11-0 | 33-21-12 | | D00342 | | | | D00344 | 9 | | | 115-199 |
| 0120 | 20 | | GA | | 5-0 | 33-21-51 | | D00346 | 10 | | | SM00020 | | 9 | | 115-199 |
| 0121 | 20 | | GA | | 5-0 | 33-21-12 | | D00346 | | | | SM00021 | | 9 | | 115-199 |
| 0122 | 20 | | GA | | 3-0 | 33-21-12 | | D00346 | | | | GD00623 | AC.R | E | | 115-199 |
| 0123 | 24 | | GK | | 5-0 | 33-21-12 | | D00346 | | | | SM00023 | | 9 | | 115-199 |
| 0124 | 20 | | GA | | 2-0 | 33-21-12 | | D00346 | | | | GD00624 | ST.R | E | | 115-199 |
| 0125 | 22 | | GA | | 14-0 | 33-21-12 | | D00346 | | | | D00348 | 5 | | | 115-199 |
| 0126 | 22 | | GA | | 14-0 | 33-21-12 | | D00346 | | | | D00348 | 6 | | | 115-199 |
| 0127 | 22 | | GA | | 14-0 | 33-21-12 | | D00346 | | | | D00348 | 7 | | | 115-199 |
| 0128 | 22 | | GA | | 14-0 | 33-21-12 | | D00346 | | | | D00348 | 8 | | | 115-199 |
| 0129 | 22 | | GA | | 14-0 | 33-21-12 | | D00346 | | | | D00348 | 9 | | | 115-199 |
| 0141 | 20 | | GA | | 9-0 | 33-21-12 | | D00356 | | | | SM00041 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3510

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|----------|---|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3514 | | 286N3514 | | | | | FLUORESCENT LIGHTING-CEILING, LEFT FORWARD (continued) | | | | | | | | |
| 0142 | 20 | GA | | | 5-0 | 33-21-12 | D00356 | | 2 | | GD00627 | AC.R | E | | 115-199 |
| 0143 | 24 | GK | | | 9-0 | 33-21-12 | D00356 | | 3 | | SM00043 | | 9 | | 115-199 |
| 0144 | 20 | GA | | | 5-0 | 33-21-12 | D00356 | | 4 | | GD00628 | ST.R | E | | 115-199 |
| 0145 | 22 | GA | | | 13-0 | 33-21-12 | D00358 | | 5 | | D00356 | | 5 | | 115-199 |
| 0146 | 22 | GA | | | 13-0 | 33-21-12 | D00358 | | 6 | | D00356 | | 6 | | 115-199 |
| 0147 | 22 | GA | | | 13-0 | 33-21-12 | D00358 | | 7 | | D00356 | | 7 | | 115-199 |
| 0148 | 22 | GA | | | 13-0 | 33-21-12 | D00358 | | 8 | | D00356 | | 8 | | 115-199 |
| 0149 | 22 | GA | | | 13-0 | 33-21-12 | D00358 | | 9 | | D00356 | | 9 | | 115-199 |
| 0301 | 20 | GA | | | 44-0 | 33-21-12 | D40376P | | 1 | | SM00011 | | 9 | | 001-099 |
| 0303 | 24 | GK | | | 44-0 | 33-21-12 | D40376P | | 3 | | SM00013 | | 9 | | 001-099 |
| 0308 | 20 | GA | | | 75-0 | SPARE | D40376P | | 8 | | D41714J | | 8 | | 001-099 |
| 0309 | 20 | GA | | | 75-0 | SPARE | D40376P | | 9 | | D41714J | | 9 | | 001-099 |
| 0310 | 20 | GA | | | 44-0 | 33-21-51 | D40376P | | 10 | | SM00010 | | 9 | | 001-099 |
| 0310 | 20 | GA | | | 44-0 | 33-21-51 | D40376P | | 4 | | SM00020 | | 9 | | 115-199 |
| 0311 | 20 | GA | | | 6-0 | 33-21-12 | SM00011 | | | 9 | SM00021 | | 9 | | 115-199 |
| 0312 | 20 | GA | | | 75-0 | SPARE | D40376P | | 12 | | D41714J | | 12 | | 001-099 |
| 0313 | 24 | GK | | | 6-0 | 33-21-12 | SM00013 | | | 9 | SM00023 | | 9 | | 115-199 |
| 0330 | 20 | GA | | | 32-0 | 33-21-51 | D41714J | | 10 | | SM00010 | | 9 | | 001-099 |
| 0330 | 20 | GA | | | 33-0 | 33-21-51 | SM00020 | | | 9 | D41714J | | 4 | | 115-199 |
| 0331 | 20 | GA | | | 11-0 | 33-21-12 | SM00031 | | | 9 | SM00041 | | 9 | | 001-099 |
| 0333 | 24 | GK | | | 5-0 | 33-21-12 | SM00033 | | | 9 | SM00043 | | 9 | | 001-099 |
| 0341 | 20 | GA | | | 10-0 | 33-21-12 | SM00041 | | | 9 | D41714J | | 7 | | 001-099 |
| 0341 | 20 | GA | | | 8-0 | 33-21-12 | SM00041 | | | 9 | D41714J | | 1 | | 115-199 |
| 0343 | 24 | GK | | | 13-0 | 33-21-12 | SM00043 | | | 9 | D41714J | | 6 | | 001-099 |
| 0343 | 24 | GK | | | 8-0 | 33-21-12 | SM00043 | | | 9 | D41714J | | 3 | | 115-199 |
| 0361 | 20 | GA | | | 1-0 | 33-21-12 | D40376P | | 1 | | SM00061 | | 9 | | 115-199 |
| 0363 | 24 | GK | | | 1-0 | 33-21-12 | D40376P | | 3 | | SM00063 | | 9 | | 115-199 |
| 0391 | 20 | GA | | | 9-0 | 33-21-12 | SM00041 | | | 9 | SM00091 | | 9 | | 115-199 |
| 0393 | 24 | GK | | | 9-0 | 33-21-12 | SM00043 | | | 9 | SM00093 | | 9 | | 115-199 |
| 0411 | 20 | GA | | | 39-0 | 33-21-12 | SM00061 | | | 9 | SM00011 | | 9 | | 115-199 |
| 0413 | 24 | GK | | | 39-0 | 33-21-12 | SM00063 | | | 9 | SM00013 | | 9 | | 115-199 |
| 0431 | 20 | GA | | | 2-0 | 33-21-12 | SM00131 | | | 9 | SM00091 | | 9 | | 115-199 |
| 0433 | 24 | GK | | | 2-0 | 33-21-12 | SM00133 | | | 9 | SM00093 | | 9 | | 115-199 |
| 0441 | 20 | GA | | | 14-0 | 33-21-12 | SM00011 | | | 9 | SM00031 | | 9 | | 001-099 |
| 0441 | 20 | GA | | | 19-0 | 33-21-12 | SM00021 | | | 9 | SM00131 | | 9 | | 115-199 |
| 0443 | 24 | GK | | | 24-0 | 33-21-12 | SM00013 | | | 9 | SM00033 | | 9 | | 001-099 |
| 0443 | 24 | GK | | | 19-0 | 33-21-12 | SM00023 | | | 9 | SM00133 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3510

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---------------------------------------|-------|----------|--------|------|--------|-------|---------|------|-------------|--------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W3516 | 286N3516 | | | | FLOURESCENT LIGHTING-CEILING,LEFT MID | | | | | | | | | | | |
| 0050 | 20 | | GA | | 4-3 | | 33-21-51 | D00360 | | | | SM00050 | | 9 | | 001-099 |
| 0050 | 20 | | GA | | 4-0 | | 33-21-51 | D00360 | | | | SM00050 | | 9 | | 115-199 |
| 0051 | 20 | | GA | | 14-7 | | 33-21-13 | D00360 | | | | SM00051 | | 9 | | 001-099 |
| 0051 | 20 | | GA | | 4-0 | | 33-21-13 | D00360 | | | | SM00051 | | 9 | | 115-199 |
| 0052 | 20 | | GA | | 3-0 | | 33-21-13 | D00360 | | | | GD00629 | AC.. | E | | 001-099 |
| 0052 | 20 | | GA | | 6-0 | | 33-21-13 | D00360 | | | | GD00629 | AC.R | E | | 115-199 |
| 0053 | 24 | | GK | | 3-11 | | 33-21-13 | D00360 | | | | SM00053 | | 9 | | 001-099 |
| 0053 | 24 | | GK | | 4-0 | | 33-21-13 | D00360 | | | | SM00053 | | 9 | | 115-199 |
| 0054 | 20 | | GA | | 3-0 | | 33-21-13 | D00360 | | | | GD00630 | ST.. | E | | 001-099 |
| 0054 | 20 | | GA | | 6-0 | | 33-21-13 | D00360 | | | | GD00630 | ST.R | E | | 115-199 |
| 0055 | 22 | | GA | | 12-3 | | 33-21-13 | D00360 | | | | D00362 | | 5 | | 001-099 |
| 0055 | 22 | | GA | | 13-0 | | 33-21-13 | D00360 | | | | D00362 | | 5 | | 115-199 |
| 0056 | 22 | | GA | | 12-3 | | 33-21-13 | D00360 | | | | D00362 | | 6 | | 001-099 |
| 0056 | 22 | | GA | | 13-0 | | 33-21-13 | D00360 | | | | D00362 | | 6 | | 115-199 |
| 0057 | 22 | | GA | | 12-3 | | 33-21-13 | D00360 | | | | D00362 | | 7 | | 001-099 |
| 0057 | 22 | | GA | | 13-0 | | 33-21-13 | D00360 | | | | D00362 | | 7 | | 115-199 |
| 0058 | 22 | | GA | | 12-3 | | 33-21-13 | D00360 | | | | D00362 | | 8 | | 001-099 |
| 0058 | 22 | | GA | | 13-0 | | 33-21-13 | D00360 | | | | D00362 | | 8 | | 115-199 |
| 0059 | 22 | | GA | | 12-3 | | 33-21-13 | D00360 | | | | D00362 | | 9 | | 001-099 |
| 0059 | 22 | | GA | | 13-0 | | 33-21-13 | D00360 | | | | D00362 | | 9 | | 115-199 |
| 0061 | 20 | | GA | | 3-2 | | 33-21-13 | D00364 | | | | SM00051 | | 9 | | 001-099 |
| 0061 | 20 | | GA | | 4-0 | | 33-21-13 | D00364 | | | | SM00061 | | 9 | | 115-199 |
| 0062 | 20 | | GA | | 2-8 | | 33-21-13 | D00364 | | | | GD00631 | AC.. | E | | 001-099 |
| 0062 | 20 | | GA | | 3-0 | | 33-21-13 | D00364 | | | | GD00631 | AC.R | E | | 115-199 |
| 0063 | 24 | | GK | | 3-2 | | 33-21-13 | D00364 | | | | SM00063 | | 9 | | 001-099 |
| 0063 | 24 | | GK | | 4-0 | | 33-21-13 | D00364 | | | | SM00063 | | 9 | | 115-199 |
| 0064 | 20 | | GA | | 2-8 | | 33-21-13 | D00364 | | | | GD00632 | ST.. | E | | 001-099 |
| 0064 | 20 | | GA | | 4-0 | | 33-21-13 | D00364 | | | | GD00632 | ST.R | E | | 115-199 |
| 0065 | 22 | | GA | | 11-3 | | 33-21-13 | D00364 | | | | D00366 | | 5 | | 001-099 |
| 0065 | 22 | | GA | | 12-0 | | 33-21-13 | D00364 | | | | D00366 | | 5 | | 115-199 |
| 0066 | 22 | | GA | | 11-3 | | 33-21-13 | D00364 | | | | D00366 | | 6 | | 001-099 |
| 0066 | 22 | | GA | | 12-0 | | 33-21-13 | D00364 | | | | D00366 | | 6 | | 115-199 |
| 0067 | 22 | | GA | | 11-3 | | 33-21-13 | D00364 | | | | D00366 | | 7 | | 001-099 |
| 0067 | 22 | | GA | | 12-0 | | 33-21-13 | D00364 | | | | D00366 | | 7 | | 115-199 |
| 0068 | 22 | | GA | | 11-3 | | 33-21-13 | D00364 | | | | D00366 | | 8 | | 001-099 |
| 0068 | 22 | | GA | | 12-0 | | 33-21-13 | D00364 | | | | D00366 | | 8 | | 115-199 |
| 0069 | 22 | | GA | | 11-3 | | 33-21-13 | D00364 | | | | D00366 | | 9 | | 001-099 |
| 0069 | 22 | | GA | | 12-0 | | 33-21-13 | D00364 | | | | D00366 | | 9 | | 115-199 |
| 0071 | 20 | | GA | | 4-0 | | 33-21-13 | D00368 | | | | SM00071 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3510

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3516 | 286N3516 | | | FLOURESCENT LIGHTING-CEILING,LEFT MID (continued) | | | | | | | | | | | |
| 0071 | 20 | GA | | | 6-0 | 33-21-13 | D00368 | | 1 | | SM00071 | | 9 | | 115-199 |
| 0072 | 20 | GA | | | 6-8 | 33-21-13 | D00368 | | 2 | | GD00633 | AC.. | E | | 001-099 |
| 0072 | 20 | GA | | | 7-0 | 33-21-13 | D00368 | | 2 | | GD00633 | AC.R | E | | 115-199 |
| 0073 | 24 | GK | | | 4-0 | 33-21-13 | D00368 | | 3 | | SM00073 | | 9 | | 001-099 |
| 0073 | 24 | GK | | | 5-0 | 33-21-13 | D00368 | | 3 | | SM00073 | | 9 | | 115-199 |
| 0074 | 20 | GA | | | 6-8 | 33-21-13 | D00368 | | 4 | | GD00634 | ST.. | E | | 001-099 |
| 0074 | 20 | GA | | | 7-0 | 33-21-13 | D00368 | | 4 | | GD00634 | ST.R | E | | 115-199 |
| 0075 | 22 | GA | | | 11-9 | 33-21-13 | D00368 | | 5 | | D04596 | | 5 | | 001-099 |
| 0075 | 22 | GA | | | 12-0 | 33-21-13 | D00368 | | 5 | | D04596 | | 5 | | 115-199 |
| 0076 | 22 | GA | | | 11-9 | 33-21-13 | D00368 | | 6 | | D04596 | | 6 | | 001-099 |
| 0076 | 22 | GA | | | 12-0 | 33-21-13 | D00368 | | 6 | | D04596 | | 6 | | 115-199 |
| 0077 | 22 | GA | | | 11-9 | 33-21-13 | D00368 | | 7 | | D04596 | | 7 | | 001-099 |
| 0077 | 22 | GA | | | 12-0 | 33-21-13 | D00368 | | 7 | | D04596 | | 7 | | 115-199 |
| 0078 | 22 | GA | | | 11-9 | 33-21-13 | D00368 | | 8 | | D04596 | | 8 | | 001-099 |
| 0078 | 22 | GA | | | 12-0 | 33-21-13 | D00368 | | 8 | | D04596 | | 8 | | 115-199 |
| 0079 | 22 | GA | | | 11-9 | 33-21-13 | D00368 | | 9 | | D04596 | | 9 | | 001-099 |
| 0079 | 22 | GA | | | 12-0 | 33-21-13 | D00368 | | 9 | | D04596 | | 9 | | 115-199 |
| 0306 | 24 | GK | | | 2-9 | 33-21-13 | D41714P | | 6 | | SM00053 | | 9 | | 001-099 |
| 0307 | 20 | GA | | | 13-4 | 33-21-13 | D41714P | | 7 | | SM00051 | | 9 | | 001-099 |
| 0308 | 20 | GA | | | 27-11 | SPARE | D41714P | | 8 | | D41716J | | 8 | | 001-099 |
| 0309 | 20 | GA | | | 11-6 | 33-21-13 | SM00051 | | 9 | | SM00071 | | 9 | | 001-099 |
| 0311 | 20 | GA | | | 27-11 | SPARE | D41714P | | 11 | | D41716J | | 11 | | 001-099 |
| 0312 | 20 | GA | | | 27-11 | SPARE | D41714P | | 12 | | D41716J | | 12 | | 001-099 |
| 0330 | 20 | GA | | | 1-9 | 33-21-51 | D41714P | | 10 | | SM00050 | | 9 | | 001-099 |
| 0330 | 20 | GA | | | 3-0 | 33-21-51 | D41714P | | 4 | | SM00050 | | 9 | | 115-199 |
| 0341 | 20 | GA | | | 3-0 | 33-21-13 | D41714P | | 1 | | SM00051 | | 9 | | 115-199 |
| 0343 | 24 | GK | | | 3-0 | 33-21-13 | D41714P | | 3 | | SM00053 | | 9 | | 115-199 |
| 0351 | 20 | GA | | | 11-0 | 33-21-13 | SM00051 | | 9 | | SM00061 | | 9 | | 115-199 |
| 0353 | 24 | GK | | | 11-2 | 33-21-13 | SM00053 | | 9 | | SM00063 | | 9 | | 001-099 |
| 0353 | 24 | GK | | | 11-0 | 33-21-13 | SM00053 | | 9 | | SM00063 | | 9 | | 115-199 |
| 0360 | 20 | GA | | | 26-9 | 33-21-51 | D41716J | | 10 | | SM00050 | | 9 | | 001-099 |
| 0360 | 20 | GA | | | 27-0 | 33-21-51 | SM00050 | | 9 | | D41716J | | 4 | | 115-199 |
| 0361 | 20 | GA | | | 10-0 | 33-21-13 | SM00061 | | 9 | | SM00071 | | 9 | | 115-199 |
| 0363 | 24 | GK | | | 11-6 | 33-21-13 | SM00063 | | 9 | | SM00073 | | 9 | | 001-099 |
| 0363 | 24 | GK | | | 11-0 | 33-21-13 | SM00063 | | 9 | | SM00073 | | 9 | | 115-199 |
| 0471 | 20 | GA | | | 4-9 | 33-21-13 | SM00071 | | 9 | | D41716J | | 9 | | 001-099 |
| 0471 | 20 | GA | | | 9-0 | 33-21-13 | SM00071 | | 9 | | D41716J | | 1 | | 115-199 |
| 0473 | 24 | GK | | | 4-9 | 33-21-13 | SM00073 | | 9 | | D41716J | | 6 | | 001-099 |
| 0473 | 24 | GK | | | 9-0 | 33-21-13 | SM00073 | | 9 | | D41716J | | 3 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3510

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|---------------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3518 | 286N3518 | | | FLUORESCENT LIGHTING-CEILING,LEFT AFT | | | | | | | | | | | |
| 0010 | 20 | | GA | | 7-0 | 33-21-51 | D00374 | | | | SM00010 | | | 9 | 001-099 |
| 0011 | 20 | | GA | | 7-0 | 33-21-14 | D00374 | | | | SM00011 | | | 9 | 001-099 |
| 0012 | 20 | | GA | | 5-0 | 33-21-14 | D00374 | | | | GD00637 | AC.. | E | | 001-099 |
| 0013 | 24 | | GK | | 7-0 | 33-21-14 | D00374 | | | | SM00013 | | | 9 | 001-099 |
| 0014 | 20 | | GA | | 5-0 | 33-21-14 | D00374 | | | | GD00638 | ST.. | E | | 001-099 |
| 0015 | 22 | | GA | | 15-0 | 33-21-14 | D00374 | | | | D00376 | | | 5 | 001-099 |
| 0016 | 22 | | GA | | 15-0 | 33-21-14 | D00374 | | | | D00376 | | | 6 | 001-099 |
| 0017 | 22 | | GA | | 15-0 | 33-21-14 | D00374 | | | | D00376 | | | 7 | 001-099 |
| 0018 | 22 | | GA | | 15-0 | 33-21-14 | D00374 | | | | D00376 | | | 8 | 001-099 |
| 0019 | 22 | | GA | | 15-0 | 33-21-14 | D00374 | | | | D00376 | | | 9 | 001-099 |
| 0020 | 20 | | GA | | 18-0 | 33-21-51 | D00380 | | | | SM00010 | | | 9 | 001-099 |
| 0021 | 20 | | GA | | 5-0 | 33-21-14 | D00380 | | | | SM00021 | | | 9 | 001-099 |
| 0022 | 20 | | GA | | 4-0 | 33-21-14 | D00380 | | | | GD00639 | AC.. | E | | 001-099 |
| 0023 | 24 | | GK | | 5-0 | 33-21-14 | D00380 | | | | SM00023 | | | 9 | 001-099 |
| 0024 | 20 | | GA | | 4-0 | 33-21-14 | D00380 | | | | GD00640 | ST.. | E | | 001-099 |
| 0025 | 22 | | GA | | 15-0 | 33-21-14 | D00380 | | | | D00378 | | | 5 | 001-099 |
| 0026 | 22 | | GA | | 15-0 | 33-21-14 | D00380 | | | | D00378 | | | 6 | 001-099 |
| 0027 | 22 | | GA | | 15-0 | 33-21-14 | D00380 | | | | D00378 | | | 7 | 001-099 |
| 0028 | 22 | | GA | | 15-0 | 33-21-14 | D00380 | | | | D00378 | | | 8 | 001-099 |
| 0029 | 22 | | GA | | 15-0 | 33-21-14 | D00380 | | | | D00378 | | | 9 | 001-099 |
| 0031 | 20 | | GA | | 12-0 | 33-21-14 | D00382 | | | | SM00021 | | | 9 | 001-099 |
| 0032 | 20 | | GA | | 5-0 | 33-21-14 | D00382 | | | | GD00641 | AC.. | E | | 001-099 |
| 0033 | 24 | | GK | | 12-0 | 33-21-14 | D00382 | | | | SM00023 | | | 9 | 001-099 |
| 0034 | 20 | | GA | | 5-0 | 33-21-14 | D00382 | | | | GD00642 | ST.. | E | | 001-099 |
| 0101 | 20 | | GA | | 6-0 | 33-21-14 | D00374 | | | | SM00101 | | | 9 | 115-199 |
| 0102 | 20 | | GA | | 4-0 | 33-21-14 | D00374 | | | | GD00637 | AC.R | E | | 115-199 |
| 0103 | 24 | | GK | | 6-0 | 33-21-14 | D00374 | | | | SM00103 | | | 9 | 115-199 |
| 0104 | 20 | | GA | | 4-0 | 33-21-14 | D00374 | | | | GD00638 | ST.R | E | | 115-199 |
| 0105 | 22 | | GA | | 14-0 | 33-21-14 | D00374 | | | | D00376 | | | 5 | 115-199 |
| 0106 | 22 | | GA | | 14-0 | 33-21-14 | D00374 | | | | D00376 | | | 6 | 115-199 |
| 0107 | 22 | | GA | | 14-0 | 33-21-14 | D00374 | | | | D00376 | | | 7 | 115-199 |
| 0108 | 22 | | GA | | 14-0 | 33-21-14 | D00374 | | | | D00376 | | | 8 | 115-199 |
| 0109 | 22 | | GA | | 14-0 | 33-21-14 | D00374 | | | | D00376 | | | 9 | 115-199 |
| 0110 | 20 | | GA | | 6-0 | 33-21-51 | D00374 | | | | SM00110 | | | 9 | 115-199 |
| 0111 | 20 | | GA | | 5-0 | 33-21-14 | D00380 | | | | SM00111 | | | 9 | 115-199 |
| 0112 | 20 | | GA | | 3-0 | 33-21-14 | D00380 | | | | GD00639 | AC.R | E | | 115-199 |
| 0113 | 24 | | GK | | 5-0 | 33-21-14 | D00380 | | | | SM00113 | | | 9 | 115-199 |
| 0114 | 20 | | GA | | 3-0 | 33-21-14 | D00380 | | | | GD00640 | ST.R | E | | 115-199 |
| 0115 | 22 | | GA | | 14-0 | 33-21-14 | D00380 | | | | D00378 | | | 5 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3510

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3518 | 286N3518 | | | FLUORESCENT LIGHTING-CEILING,LEFT AFT (continued) | | | | | | | | | | | |
| 0116 | 22 | | GA | | 14-0 | 33-21-14 | D00380 | | 6 | | D00378 | | 6 | | 115-199 |
| 0117 | 22 | | GA | | 14-0 | 33-21-14 | D00380 | | 7 | | D00378 | | 7 | | 115-199 |
| 0118 | 22 | | GA | | 14-0 | 33-21-14 | D00380 | | 8 | | D00378 | | 8 | | 115-199 |
| 0119 | 22 | | GA | | 14-0 | 33-21-14 | D00380 | | 9 | | D00378 | | 9 | | 115-199 |
| 0120 | 20 | | GA | | 21-0 | 33-21-51 | D00380 | | 10 | | SM00110 | | 9 | | 115-199 |
| 0121 | 20 | | GA | | 9-0 | 33-21-14 | D00382 | | 1 | | SM00111 | | 9 | | 115-199 |
| 0122 | 20 | | GA | | 4-0 | 33-21-14 | D00382 | | 2 | | GD00641 | AC.R | E | | 115-199 |
| 0123 | 24 | | GK | | 9-0 | 33-21-14 | D00382 | | 3 | | SM00113 | | 9 | | 115-199 |
| 0124 | 20 | | GA | | 4-0 | 33-21-14 | D00382 | | 4 | | GD00642 | ST.R | E | | 115-199 |
| 0306 | 24 | | GK | | 14-0 | 33-21-14 | D41716P | | 6 | | SM00013 | | 9 | | 001-099 |
| 0309 | 20 | | GA | | 14-0 | 33-21-14 | D41716P | | 9 | | SM00011 | | 9 | | 001-099 |
| 0310 | 20 | | GA | | 14-0 | 33-21-51 | D41716P | | 10 | | SM00010 | | 9 | | 001-099 |
| 0311 | 20 | | GA | | 14-0 | 33-21-14 | SM00011 | | | 9 | SM00021 | | 9 | | 001-099 |
| 0313 | 24 | | GK | | 14-0 | 33-21-14 | SM00013 | | | 9 | SM00023 | | 9 | | 001-099 |
| 0360 | 20 | | GA | | 11-0 | 33-21-51 | D41716P | | 4 | | SM00110 | | 9 | | 115-199 |
| 0381 | 20 | | GA | | 11-0 | 33-21-14 | D41716P | | 1 | | SM00101 | | 9 | | 115-199 |
| 0383 | 24 | | GK | | 11-0 | 33-21-14 | D41716P | | 3 | | SM00103 | | 9 | | 115-199 |
| 0401 | 20 | | GA | | 18-0 | 33-21-14 | SM00101 | | | 9 | SM00111 | | 9 | | 115-199 |
| 0403 | 24 | | GK | | 18-0 | 33-21-14 | SM00103 | | | 9 | SM00113 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3510

Page 7 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3525 | 286N3525 | | | ATTENDANT HANDSETS | | | | | | | | | | | |
| 4251B | 24 | G4 | AA | | 40-0 | 23-42-11 | D00691 | | 3 | | D41551P | 2 | | | 001-099 |
| 4251B | 24 | G4 | AA | | 37-0 | 23-42-11 | D41891J | | 3 | | D41551P | 2 | | | 115-199 |
| 4251G | 24 | G4 | AA | | 0-0 | 23-42-11 | D00691 | | 5 | | D41551P | 4 | | | 001-099 |
| 4251G | 24 | G4 | AA | | 0-0 | 23-42-11 | D41891J | | 5 | | D41551P | 4 | | | 115-199 |
| 4251R | 24 | G4 | AA | | 0-0 | 23-42-11 | D00691 | | 1 | | D41551P | 1 | | | 001-099 |
| 4251R | 24 | G4 | AA | | 0-0 | 23-42-11 | D41891J | | 1 | | D41551P | 1 | | | 115-199 |
| 4251Y | 24 | G4 | AA | | 0-0 | 23-42-11 | D00691 | | 4 | | D41551P | 3 | | | 001-099 |
| 4251Y | 24 | G4 | AA | | 0-0 | 23-42-11 | D41891J | | 4 | | D41551P | 3 | | | 115-199 |
| 4251Z | | | AA | | 0-0 | 23-42-11 | D00691 | | 2 | | D41551P | 5 | | | 001-099 |
| 4251Z | | | AA | | 0-0 | 23-42-11 | D41891J | | 2 | | D41551P | 5 | | | 115-199 |
| 4252B | 24 | G4 | AB | | 120-0 | 23-42-11 | D41893J | | 3 | | D41551P | 7 | | | 001-099 |
| 4252B | 24 | G4 | AB | | 115-0 | 23-42-11 | D41893J | | 3 | | D41551P | 7 | | | 115-199 |
| 4252G | 24 | G4 | AB | | 0-0 | 23-42-11 | D41893J | | 5 | | D41551P | 18 | | | ALL |
| 4252R | 24 | G4 | AB | | 0-0 | 23-42-11 | D41893J | | 1 | | D41551P | 6 | | | ALL |
| 4252Y | 24 | G4 | AB | | 0-0 | 23-42-11 | D41893J | | 4 | | D41551P | 17 | | | ALL |
| 4252Z | | | AB | | 0-0 | 23-42-11 | D41893J | | 2 | | D41551P | 16 | | | ALL |
| 4253B | 24 | G4 | AC | | 93-0 | 23-42-11 | D00837 | | 3 | | D41551P | 12 | | | 001-099 |
| 4253B | 24 | G4 | AC | | 86-0 | 23-42-11 | D00837 | | 3 | | D41551P | 12 | | | 115-199 |
| 4253G | 24 | G4 | AC | | 0-0 | 23-42-11 | D00837 | | 5 | | D41551P | 25 | | | ALL |
| 4253R | 24 | G4 | AC | | 0-0 | 23-42-11 | D00837 | | 1 | | D41551P | 11 | | | ALL |
| 4253Y | 24 | G4 | AC | | 0-0 | 23-42-11 | D00837 | | 4 | | D41551P | 24 | | | ALL |
| 4253Z | | | AC | | 0-0 | 23-42-11 | D00837 | | 2 | | D41551P | 13 | | | ALL |
| 4254B | 24 | G4 | AD | | 42-0 | 23-42-11 | D00915 | | 3 | | D41551P | 15 | | | 001-099 |
| 4254B | 24 | G4 | AD | | 38-0 | 23-42-11 | D00765 | | 3 | | D41551P | 15 | | | 115-199 |
| 4254G | 24 | G4 | AD | | 0-0 | 23-42-11 | D00915 | | 5 | | D41551P | 27 | | | 001-099 |
| 4254G | 24 | G4 | AD | | 0-0 | 23-42-11 | D00765 | | 5 | | D41551P | 27 | | | 115-199 |
| 4254R | 24 | G4 | AD | | 0-0 | 23-42-11 | D00915 | | 1 | | D41551P | 14 | | | 001-099 |
| 4254R | 24 | G4 | AD | | 0-0 | 23-42-11 | D00765 | | 1 | | D41551P | 14 | | | 115-199 |
| 4254Y | 24 | G4 | AD | | 0-0 | 23-42-11 | D00915 | | 4 | | D41551P | 26 | | | 001-099 |
| 4254Y | 24 | G4 | AD | | 0-0 | 23-42-11 | D00765 | | 4 | | D41551P | 26 | | | 115-199 |
| 4254Z | | | AD | | 0-0 | 23-42-11 | D00915 | | 2 | | D41551P | 28 | | | 001-099 |
| 4254Z | | | AD | | 0-0 | 23-42-11 | D00765 | | 2 | | D41551P | 28 | | | 115-199 |
| 4255B | 24 | G4 | AE | | 35-0 | 23-42-11 | D00839 | | 3 | | D41551P | 30 | | | 115-199 |
| 4255G | 24 | G4 | AE | | 0-0 | 23-42-11 | D00839 | | 5 | | D41551P | 22 | | | 115-199 |
| 4255R | 24 | G4 | AE | | 0-0 | 23-42-11 | D00839 | | 1 | | D41551P | 29 | | | 115-199 |
| 4255Y | 24 | G4 | AE | | 0-0 | 23-42-11 | D00839 | | 4 | | D41551P | 31 | | | 115-199 |
| 4255Z | | | AE | | 0-0 | 23-42-11 | D00839 | | 2 | | D41551P | 23 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3520

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | |
|------------------------|-------------|----|----|-------|--|---------|---------|------|------|--------|---------|------|------|-------------|--------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice |
| W3532 | 286N3532 | | | | OVERHEAD DISC TO EMERGENCY LIGHTS-LEFT FORWARD AND MID FORWARD | | | | | | | | | | |
| 0001 | 16 | | GA | 3-0 | 33-51-12 | D00068 | | 1 | 16 | | GD00478 | DC.. | E | ALL | |
| 0002 | 22 | | GA | 5-5 | 33-51-12 | D00068 | | 2 | | | SP01592 | | 9 | 001-099 | |
| 0002 | 22 | | GA | 5-0 | 33-51-12 | D00068 | | 2 | | | SP01592 | | 9 | 115-199 | |
| 0003 | 22 | | GA | 4-8 | 33-51-12 | D00068 | | 3 | | | SM00001 | | 9 | 001-099 | |
| 0003 | 22 | | GA | 7-0 | 33-51-12 | D00068 | | 3 | | | SM00001 | | 9 | 115-199 | |
| 0004 | 22 | | GA | 4-8 | 33-51-12 | D00068 | | 4 | | | SM00002 | | 9 | 001-099 | |
| 0004 | 22 | | GA | 7-0 | 33-51-12 | D00068 | | 4 | | | SM00002 | | 9 | 115-199 | |
| 0005 | 16 | | GA | 0-7 | 33-51-12 | D00068 | | 5 | 16 | | D00068 | 6 | 16 | 001-099 | |
| 0005 | 22 | | GA | 1-0 | 33-51-12 | D00068 | | 5 | | | D00068 | 6 | | 115-199 | |
| 0007 | 20 | | GA | 3-2 | 33-51-12 | D00068 | | 7 | | | GD00479 | ST.. | E | 001-099 | |
| 0007 | 20 | | GA | 3-0 | 33-51-12 | D00068 | | 7 | | | GD00479 | ST.. | E | 115-199 | |
| 0008 | 24 | | GK | 5-5 | 33-51-12 | D00068 | | 8 | | | SP01070 | | 9 | 001-099 | |
| 0008 | 24 | | GK | 5-0 | 33-51-12 | D00068 | | 8 | | | SP01070 | | 9 | 115-199 | |
| 0009 | 16 | | GA | 15-11 | 33-51-12 | D00068 | | 9 | 16 | | D04472 | 1 | VY | 001-099 | |
| 0009 | 18 | | GA | 17-0 | 33-51-12 | D00068 | | 9 | 18 | | D04472 | 1 | VY | 115-199 | |
| 0010 | 20 | | GA | 34-0 | 33-51-12 | D00068 | | 10 | | | D07516 | 1 | VG | 115-199 | |
| 0011 | 20 | | GA | 9-5 | 33-51-12 | D00068 | | 11 | | | D04532 | 1 | VY | 001-099 | |
| 0011 | 22 | | GA | 11-0 | 33-51-12 | D00068 | | 11 | | | D04532 | 1 | VY | 115-199 | |
| 0014 | 20 | | GA | 25-0 | 33-51-12 | D00068 | | 14 | | | D07512 | 1 | VG | 115-199 | |
| 0015 | 22 | | GA | 19-4 | 33-51-12 | D00068 | | 15 | | | D07508 | 1 | VG | 001-099 | |
| 0016 | 20 | | GA | 24-7 | 33-51-12 | D00068 | | 16 | | | D07512 | 1 | VG | 001-099 | |
| 0020 | 22 | | GA | 0-7 | 33-51-12 | D00068 | | 20 | | | D00068 | 24 | | 001-099 | |
| 0020 | 22 | | GA | 2-0 | 33-51-12 | D00068 | | 20 | | | D00068 | 24 | | 115-199 | |
| 0033 | 22 | | GA | 5-3 | 33-51-12 | D40354J | | 3 | | | SM00001 | | 9 | 001-099 | |
| 0033 | 22 | | GA | 4-0 | 33-51-12 | D40354J | | 3 | | | SM00001 | | 9 | 115-199 | |
| 0034 | 22 | | GA | 5-3 | 33-51-12 | D40354J | | 4 | | | SM00002 | | 9 | 001-099 | |
| 0034 | 22 | | GA | 4-0 | 33-51-12 | D40354J | | 4 | | | SM00002 | | 9 | 115-199 | |
| 0035 | 22 | | GA | 11-3 | 33-51-12 | SP01070 | | | 9 | | S10292 | C | Z1 | 001-099 | |
| 0035 | 22 | | GA | 13-0 | 33-51-12 | SP01070 | | | 9 | | S10292 | C | Z1 | 115-199 | |
| 0036 | 22 | | GA | 4-9 | 33-51-12 | S10292 | | NO | Z1 | | GD01420 | DC.. | E | 001-099 | |
| 0036 | 22 | | GA | 6-0 | 33-51-12 | S10292 | | NO | Z1 | | GD01420 | DC.. | E | 115-199 | |
| 0037 | 22 | | GA | 9-7 | 33-51-13 | SP00290 | | | 9 | | S10293 | C | Z1 | 001-099 | |
| 0037 | 22 | | GA | 11-0 | 33-51-13 | SP00290 | | | 9 | | S10293 | C | Z1 | 115-199 | |
| 0038 | 22 | | GA | 3-5 | 33-51-13 | S10293 | | NO | Z1 | | GD01421 | DC.. | E | 001-099 | |
| 0038 | 22 | | GA | 4-0 | 33-51-13 | S10293 | | NO | Z1 | | GD01421 | DC.. | E | 115-199 | |
| 0040 | 20 | | GA | 33-2 | SPARE | D40354J | | | 5 | | D00072 | CAP | Y | 001-099 | |
| 0040 | 20 | | GA | 35-0 | SPARE | D40354J | | | 5 | | D00072 | CAP | Y | 115-199 | |
| 0041 | 20 | | GA | 33-2 | SPARE | D40354J | | | 6 | | D00072 | CAP | Y | 001-099 | |
| 0041 | 20 | | GA | 35-0 | SPARE | D40354J | | | 6 | | D00072 | CAP | Y | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W3530

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3532 | 286N3532 | | | | OVERHEAD DISC TO EMERGENCY LIGHTS-LEFT FORWARD AND MID FORWARD (continued) | | | | | | | | | | |
| 0051 | 20 | | GA | | 3-4 | 33-51-12 | GD00467 | DC.. | E | | D04534 | 1 | VG | | 001-099 |
| 0051 | 20 | | GA | | 3-0 | 33-51-12 | GD00467 | DC.. | E | | D04534 | 1 | VG | | 115-199 |
| 0053 | 20 | | GA | | 4-7 | 33-51-21 | D07294 | | 1 | VG | GD03298 | DC.. | E | | 001-099 |
| 0054 | 20 | | GA | | 7-0 | 33-51-12 | GD00470 | DC.. | E | | D07514 | 1 | VY | | 115-199 |
| 0055 | 20 | | GA | | 6-2 | 33-51-12 | GD00469 | DC.. | E | | D07510 | 1 | VY | | 001-099 |
| 0055 | 20 | | GA | | 4-0 | 33-51-12 | GD00471 | DC.. | E | | D07518 | 1 | VY | | 115-199 |
| 0056 | 20 | | GA | | 6-8 | 33-51-12 | D07514 | | 1 | VY | GD00470 | DC.. | E | | 001-099 |
| 0059 | 20 | | GA | | 3-5 | 33-51-12 | GD00499 | DC.. | E | | D04470 | 1 | VG | | 001-099 |
| 0059 | 20 | | GA | | 3-0 | 33-51-12 | GD00499 | DC.. | E | | D04470 | 1 | VG | | 115-199 |
| 0101 | 16 | | GA | | 3-0 | 33-51-13 | GD00480 | DC.. | E | | D00072 | 1 | 16 | | ALL |
| 0102 | 22 | | GA | | 9-6 | 33-51-13 | D00072 | | 2 | | SP01072 | | 9 | | 001-099 |
| 0102 | 22 | | GA | | 10-0 | 33-51-13 | D00072 | | 2 | | SP01072 | | 9 | | 115-199 |
| 0103 | 22 | | GA | | 36-2 | 33-51-13 | SM00001 | | | 9 | D00072 | | 3 | | 001-099 |
| 0103 | 22 | | GA | | 36-0 | 33-51-13 | SM00001 | | | 9 | D00072 | | 3 | | 115-199 |
| 0104 | 22 | | GA | | 36-2 | 33-51-13 | SM00002 | | | 9 | D00072 | | 4 | | 001-099 |
| 0104 | 22 | | GA | | 36-0 | 33-51-13 | SM00002 | | | 9 | D00072 | | 4 | | 115-199 |
| 0105 | 16 | | GA | | 0-7 | 33-51-13 | D00072 | | 5 | 16 | D00072 | | 6 | 16 | 001-099 |
| 0105 | 22 | | GA | | 1-0 | 33-51-13 | D00072 | | 5 | | D00072 | | 6 | | 115-199 |
| 0107 | 20 | | GA | | 3-4 | 33-51-13 | D00072 | | 7 | | GD00481 | ST.. | E | | 001-099 |
| 0107 | 20 | | GA | | 4-0 | 33-51-13 | D00072 | | 7 | | GD00481 | ST.. | E | | 115-199 |
| 0108 | 24 | | GK | | 9-6 | 33-51-13 | D00072 | | 8 | | SP00290 | | 9 | | 001-099 |
| 0108 | 24 | | GK | | 10-0 | 33-51-13 | D00072 | | 8 | | SP00290 | | 9 | | 115-199 |
| 0109 | 18 | | GA | | 15-3 | 33-51-13 | D00072 | | 9 | 18 | D04480 | 1 | VY | | 001-099 |
| 0109 | 18 | | GA | | 16-0 | 33-51-13 | D00072 | | 9 | 18 | D04480 | 1 | VY | | 115-199 |
| 0110 | 20 | | GA | | 35-3 | 33-51-21 | D00068 | | 10 | | D06390 | 2 | | | 001-099 |
| 0111 | 20 | | GA | | 2-2 | 33-51-13 | D00072 | | 11 | | D04548 | 1 | VY | | 001-099 |
| 0111 | 20 | | GA | | 4-0 | 33-51-13 | D00072 | | 11 | | D04548 | 1 | VY | | 115-199 |
| 0112 | 22 | | GA | | 21-0 | 33-51-13 | D00072 | | 12 | | D07500 | 1 | VG | | 115-199 |
| 0113 | 22 | | GA | | 18-0 | 33-51-13 | D00072 | | 13 | | D07516 | 1 | VG | | 001-099 |
| 0113 | 22 | | GA | | 19-0 | 33-51-13 | D00072 | | 13 | | D07524 | 1 | VG | | 115-199 |
| 0114 | 22 | | GA | | 17-9 | 33-51-13 | D00072 | | 14 | | D07524 | 1 | VG | | 001-099 |
| 0114 | 22 | | GA | | 32-6 | 33-51-13 | D00072 | | 10 | | D07504 | 1 | VG | | 115-199 |
| 0115 | 20 | | GA | | 27-4 | 33-51-13 | D00072 | | 15 | | D07532 | 1 | VG | | 001-099 |
| 0116 | 20 | | GA | | 38-11 | 33-51-13 | D00072 | | 16 | | D07528 | 1 | VG | | 001-099 |
| 0116 | 22 | | GA | | 28-0 | 33-51-13 | D00072 | | 16 | | D07520 | 1 | VG | | 115-199 |
| 0120 | 22 | | GA | | 0-7 | 33-51-13 | D00072 | | 20 | | D00072 | 24 | | | 001-099 |
| 0120 | 22 | | GA | | 2-0 | 33-51-13 | D00072 | | 20 | | D00072 | 24 | | | 115-199 |
| 0151 | 20 | | GA | | 4-10 | 33-51-13 | GD00473 | DC.. | E | | D04550 | 1 | VG | | 001-099 |
| 0151 | 20 | | GA | | 5-0 | 33-51-13 | GD00473 | DC.. | E | | D04550 | 1 | VG | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3530

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3532 | | 286N3532 | | | | OVERHEAD DISC TO EMERGENCY LIGHTS-LEFT FORWARD AND MID FORWARD (continued) | | | | | | | | | |
| 0152 | 20 | GA | | | 12-0 | 33-51-13 | D07502 | 1 | VY | | GD00505 | DC.. | E | | 115-199 |
| 0153 | 20 | GA | | | 3-5 | 33-51-13 | GD00471 | DC.. | E | | D07518 | 1 | VY | | 001-099 |
| 0153 | 20 | GA | | | 5-0 | 33-51-13 | GD00475 | DC.. | E | | D07526 | 1 | VY | | 115-199 |
| 0154 | 20 | GA | | | 3-7 | 33-51-13 | GD00475 | DC.. | E | | D07526 | 1 | VY | | 001-099 |
| 0154 | 20 | GA | | | 5-0 | 33-51-13 | GD00501 | DC.. | E | | D07506 | 1 | VY | | 115-199 |
| 0155 | 20 | GA | | | 4-1 | 33-51-13 | GD00476 | DC.. | E | | D07534 | 1 | VY | | 001-099 |
| 0156 | 20 | GA | | | 9-0 | 33-51-13 | D07530 | 1 | VY | | GD00477 | DC.. | E | | 001-099 |
| 0156 | 20 | GA | | | 5-0 | 33-51-13 | D07522 | 1 | VY | | GD00506 | DC.. | E | | 115-199 |
| 0159 | 20 | GA | | | 1-7 | 33-51-13 | GD00504 | DC.. | E | | D04478 | 1 | VG | | 001-099 |
| 0159 | 20 | GA | | | 2-0 | 33-51-13 | GD00504 | DC.. | E | | D04478 | 1 | VG | | 115-199 |
| 0160 | 22 | GA | | | 7-6 | 33-51-12 | D00068 | 13 | | | D40354J | 7 | | | 001-099 |
| 0160 | 22 | GA | | | 10-0 | 33-51-12 | D00068 | 12 | | | D40354J | 7 | | | 115-199 |
| 0501 | 20 | GA | | | 36-3 | 33-51-21 | D06390 | 1 | | | SP01350 | | 9 | | 001-099 |
| 0501 | 20 | GA | | | 38-0 | 33-51-21 | D06390 | 1 | | | SP01350 | | 9 | | 115-199 |
| 0502 | 22 | GA | | | 20-1 | 33-51-21 | D07266 | 1 | VY | | D00068 | 12 | | | 001-099 |
| 0502 | 20 | GA | | | 38-0 | 33-51-21 | D06390 | 2 | | | D00068 | 13 | | | 115-199 |
| 0503 | 20 | GA | | | 36-3 | 33-51-21 | D06390 | 3 | | | SP01348 | | 9 | | 001-099 |
| 0503 | 20 | GA | | | 38-0 | 33-51-21 | D06390 | 3 | | | SP01348 | | 9 | | 115-199 |
| 0504 | 20 | GA | | | 1-11 | 33-51-21 | D06390 | 4 | | | GD03710 | DC.. | E | | 001-099 |
| 0504 | 20 | GA | | | 2-0 | 33-51-21 | D06390 | 4 | | | GD03710 | DC.. | E | | 115-199 |
| 0505 | 20 | GA | | | 1-11 | 33-51-21 | D06390 | 5 | | | GD03710 | DC.. | E | | 001-099 |
| 0505 | 20 | GA | | | 2-0 | 33-51-21 | D06390 | 5 | | | GD03710 | DC.. | E | | 115-199 |
| 0506 | 20 | GA | | | 1-11 | 33-51-21 | D06390 | 6 | | | GD03710 | DC.. | E | | 001-099 |
| 0506 | 20 | GA | | | 2-0 | 33-51-21 | D06390 | 6 | | | GD03710 | DC.. | E | | 115-199 |
| 0510 | 20 | GA | | | 30-3 | 33-51-21 | D00072 | 10 | | | D06392 | 1 | | | 001-099 |
| 0512 | 22 | GA | | | 21-3 | 33-51-21 | D00072 | 12 | | | D07270 | 1 | VY | | 001-099 |
| 0513 | 20 | GA | | | 30-0 | 33-51-21 | D00072 | 14 | | | D06392 | 1 | | | 115-199 |
| 0514 | 20 | GA | | | 42-0 | 33-51-22 | D06392 | 2 | | | SP01354 | | 9 | | ALL |
| 0515 | 20 | GA | | | 2-5 | 33-51-21 | D06392 | 4 | | | GD03712 | DC.. | E | | 001-099 |
| 0515 | 20 | GA | | | 2-0 | 33-51-21 | D06392 | 4 | | | GD03712 | DC.. | E | | 115-199 |
| 0516 | 20 | GA | | | 2-5 | 33-51-22 | D06392 | 5 | | | GD03712 | DC.. | E | | 001-099 |
| 0516 | 20 | GA | | | 2-0 | 33-51-22 | D06392 | 5 | | | GD03712 | DC.. | E | | 115-199 |
| 0517 | 22 | GA | | | 22-0 | 33-51-21 | D00068 | 15 | | | D07268 | 1 | VY | | 115-199 |
| 0518 | 20 | GA | | | 7-0 | 33-51-21 | D07296 | 1 | VG | | GD03300 | DC.. | E | | 115-199 |
| 0519 | 22 | GA | | | 22-0 | 33-51-21 | D00072 | 15 | | | D07272 | 1 | VY | | 115-199 |
| 0520 | 20 | GA | | | 5-0 | 33-51-21 | D07298 | 1 | VG | | GD03304 | DC.. | E | | 001-099 |
| 0520 | 20 | GA | | | 9-0 | 33-51-21 | D07300 | 1 | VG | | GD03308 | DC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3530

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3533 | 286N3533 | | | ATTENDANT HANDSET JUMPER | | | | | | | | | | | |
| 4251B | 24 | G4 | AA | | 6-0 | 23-42-11 | D42209P | 3 | | | D00915 | 3 | | | 115-199 |
| 4251G | 24 | G4 | AA | | 0-0 | 23-42-11 | D42209P | 5 | | | D00915 | 5 | | | 115-199 |
| 4251R | 24 | G4 | AA | | 0-0 | 23-42-11 | D42209P | 1 | | | D00915 | 1 | | | 115-199 |
| 4251Y | 24 | G4 | AA | | 0-0 | 23-42-11 | D42209P | 4 | | | D00915 | 4 | | | 115-199 |
| 4251Z | | | AA | | 0-0 | 23-42-11 | D42209P | 2 | | | D00915 | 2 | | | 115-199 |
| W3534 | 286N3534 | | | OVERHEAD DISC TO EMERGENCY LIGHTS-LEFT AFT AND MID AFT | | | | | | | | | | | |
| 0001 | 16 | GA | | | 3-0 | 33-51-14 | D00076 | 1 | 16 | | GD00493 | DC.. | E | | ALL |
| 0002 | 22 | GA | | | 17-11 | 33-51-14 | D00076 | 2 | | | SP01152 | | 9 | | ALL |
| 0003 | 22 | GA | | | 13-4 | 33-51-14 | SM00001 | | 9 | | D00076 | | 3 | | ALL |
| 0004 | 22 | GA | | | 13-4 | 33-51-14 | SM00002 | | 9 | | D00076 | | 4 | | ALL |
| 0005 | 16 | GA | | | 0-7 | 33-51-14 | D00076 | 5 | 16 | | D00076 | 6 | 16 | | 001-099 |
| 0005 | 22 | GA | | | 0-7 | 33-51-14 | D00076 | 5 | | | D00076 | 6 | | | 115-199 |
| 0007 | 20 | GA | | | 3-2 | 33-51-14 | D00076 | 7 | | | GD00494 | ST.. | E | | ALL |
| 0008 | 24 | GK | | | 17-11 | 33-51-14 | D00076 | 8 | | | SP00286 | | 9 | | ALL |
| 0009 | 18 | GA | | | 17-0 | 33-51-14 | D00076 | 9 | 18 | | D04488 | 1 | VY | | ALL |
| 0010 | 20 | GA | | | 30-8 | 33-51-22 | D06394 | 2 | | | D00076 | 10 | | | 001-099 |
| 0011 | 20 | GA | | | 3-4 | 33-51-14 | D00076 | 11 | | | D04560 | 1 | VY | | 001-099 |
| 0011 | 22 | GA | | | 3-4 | 33-51-14 | D00076 | 11 | | | D04560 | 1 | VY | | 115-199 |
| 0012 | 22 | GA | | | 26-4 | 33-51-22 | D00076 | 12 | | | D07286 | 1 | VY | | 001-099 |
| 0014 | 20 | GA | | | 25-7 | 33-51-14 | D00076 | 14 | | | D07540 | 1 | VG | | 115-199 |
| 0015 | 22 | GA | | | 27-5 | 33-51-14 | D00076 | 15 | | | D07536 | 1 | VG | | 115-199 |
| 0016 | 20 | GA | | | 27-5 | 33-51-14 | D00076 | 16 | | | D07536 | 1 | VG | | 001-099 |
| 0020 | 22 | GA | | | 0-7 | 33-51-14 | D00076 | 20 | | | D00076 | 24 | | | ALL |
| 0033 | 22 | GA | | | 75-4 | 33-51-14 | D40356J | 3 | | | SM00001 | | 9 | | ALL |
| 0034 | 22 | GA | | | 75-4 | 33-51-14 | D40356J | 4 | | | SM00002 | | 9 | | ALL |
| 0035 | 22 | GA | | | 18-0 | 33-51-14 | S10294 | | C | Z1 | SP00286 | | 9 | | ALL |
| 0036 | 22 | GA | | | 3-2 | 33-51-14 | S10294 | | NO | Z1 | GD01422 | DC.. | E | | ALL |
| 0037 | 22 | GA | | | 13-3 | 33-51-15 | S10295 | | C | Z1 | SP00294 | | 9 | | ALL |
| 0038 | 22 | GA | | | 3-4 | 33-51-15 | S10295 | | NO | Z1 | GD00489 | DC.. | E | | ALL |
| 0040 | 20 | GA | | | 114-0 | SPARE | D40356J | 5 | | | D00080 | | Y | | 001-099 |
| 0040 | 20 | GA | | | 113-8 | SPARE | D40356J | 5 | | | D00080 | | Y | | 115-199 |
| 0041 | 20 | GA | | | 114-0 | SPARE | D40356J | 6 | | | D00080 | CAP | Y | | 001-099 |
| 0041 | 20 | GA | | | 113-8 | SPARE | D40356J | 6 | | | D00080 | CAP | Y | | 115-199 |
| 0051 | 20 | GA | | | 3-5 | 33-51-14 | D04562 | 1 | VG | | GD00484 | DC.. | E | | ALL |
| 0054 | 20 | GA | | | 5-3 | 33-51-14 | D07542 | 1 | VY | | GD00485 | DC.. | E | | 115-199 |
| 0055 | 20 | GA | | | 6-4 | 33-51-14 | D07538 | 1 | VY | | GD00486 | DC.. | E | | 115-199 |
| 0056 | 20 | GA | | | 6-4 | 33-51-14 | D07538 | 1 | VY | | GD00486 | DC.. | E | | 001-099 |
| 0059 | 20 | GA | | | 2-0 | 33-51-14 | D04486 | 1 | VG | | GD00519 | DC.. | E | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3530

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3534 | 286N3534 | | | OVERHEAD DISC TO EMERGENCY LIGHTS-LEFT AFT AND MID AFT (continued) | | | | | | | | | | | |
| 0059 | 20 | | GA | | 2-6 | 33-51-14 | D04486 | 1 | VG | | GD00519 | DC.. | E | | 115-199 |
| 0101 | 16 | | GA | | 3-0 | 33-51-15 | D00080 | 1 | 16 | | GD00495 | DC.. | E | | ALL |
| 0102 | 22 | | GA | | 44-7 | 33-51-15 | D00080 | 2 | | | SP01152 | | 9 | | 001-099 |
| 0102 | 22 | | GA | | 44-2 | 33-51-15 | D00080 | 2 | | | SP01152 | | 9 | | 115-199 |
| 0103 | 22 | | GA | | 39-11 | 33-51-15 | D00080 | 3 | | | SM00001 | | 9 | | 001-099 |
| 0103 | 22 | | GA | | 39-7 | 33-51-15 | D00080 | 3 | | | SM00001 | | 9 | | 115-199 |
| 0104 | 22 | | GA | | 39-11 | 33-51-15 | D00080 | 4 | | | SM00002 | | 9 | | 001-099 |
| 0104 | 22 | | GA | | 39-7 | 33-51-15 | D00080 | 4 | | | SM00002 | | 9 | | 115-199 |
| 0105 | 16 | | GA | | 0-7 | 33-51-15 | D00080 | 5 | 16 | | D00080 | 6 | 16 | | 001-099 |
| 0105 | 22 | | GA | | 0-7 | 33-51-15 | D00080 | 5 | | | D00080 | 6 | | | 115-199 |
| 0107 | 20 | | GA | | 3-5 | 33-51-15 | D00080 | 7 | | | GD00496 | ST.. | E | | 001-099 |
| 0107 | 20 | | GA | | 3-1 | 33-51-15 | D00080 | 7 | | | GD00496 | ST.. | E | | 115-199 |
| 0108 | 24 | | GK | | 12-5 | 33-51-15 | D00080 | 8 | | | SP00294 | | 9 | | 001-099 |
| 0108 | 24 | | GK | | 12-1 | 33-51-15 | D00080 | 8 | | | SP00294 | | 9 | | 115-199 |
| 0109 | 18 | | GA | | 14-0 | 33-51-15 | D00080 | 9 | 18 | | D04504 | 1 | VY | | ALL |
| 0110 | 20 | | GA | | 6-0 | 33-51-15 | D00080 | 10 | | | SP00306 | | 9 | | 115-199 |
| 0111 | 20 | | GA | | 7-4 | 33-51-15 | D00080 | 11 | | | D04568 | 1 | VY | | 001-099 |
| 0111 | 22 | | GA | | 7-1 | 33-51-15 | D00080 | 11 | | | D04568 | 1 | VY | | 115-199 |
| 0113 | 20 | | GA | | 16-11 | 33-51-14 | D00076 | 13 | | | SP01908 | | 9 | | 001-099 |
| 0113 | 22 | | GA | | 22-1 | 33-51-14 | D00076 | 13 | | | D07568 | 1 | VG | | 115-199 |
| 0114 | 22 | | GA | | 20-7 | 33-51-15 | D00080 | 14 | | | D07564 | 1 | VG | | 115-199 |
| 0115 | 20 | | GA | | 31-3 | 33-51-15 | D00080 | 15 | | | D07568 | 1 | VG | | 001-099 |
| 0116 | 22 | | GA | | 21-0 | 33-51-15 | D00080 | 16 | | | D07564 | 1 | VG | | 001-099 |
| 0120 | 22 | | GA | | 0-7 | 33-51-15 | D00080 | 20 | | | D00080 | 24 | | | ALL |
| 0151 | 20 | | GA | | 2-4 | 33-51-15 | D04570 | 1 | VG | | GD00489 | DC.. | E | | 001-099 |
| 0151 | 20 | | GA | | 2-5 | 33-51-15 | D04570 | 1 | VG | | GD00489 | DC.. | E | | 115-199 |
| 0153 | 20 | | GA | | 12-0 | 33-51-14 | D07570 | 1 | VY | | GD00492 | DC.. | E | | 115-199 |
| 0154 | 20 | | GA | | 6-3 | 33-51-15 | D07566 | 1 | VY | | GD00491 | DC.. | E | | 115-199 |
| 0155 | 20 | | GA | | 8-0 | 33-51-15 | D07570 | 1 | VY | | GD00492 | DC.. | E | | 001-099 |
| 0156 | 20 | | GA | | 6-4 | 33-51-15 | D07566 | 1 | VY | | GD00491 | DC.. | E | | 001-099 |
| 0159 | 20 | | GA | | 2-9 | 33-51-15 | D04502 | 1 | VG | | GD00523 | DC.. | E | | ALL |
| 0505 | 20 | | GA | | 33-5 | 33-51-22 | D06394 | 1 | | | SP01356 | | 9 | | ALL |
| 0506 | 20 | | GA | | 30-8 | 33-51-22 | D06394 | 2 | | | D00076 | 12 | | | 115-199 |
| 0507 | 20 | | GA | | 1-9 | 33-51-22 | D06394 | 4 | | | GD03714 | DC.. | E | | ALL |
| 0508 | 20 | | GA | | 1-9 | 33-51-22 | D06394 | 5 | | | GD03714 | DC.. | E | | ALL |
| 0509 | 20 | | GA | | 30-5 | 33-51-22 | D06396 | 3 | | | SP01358 | | 9 | | 001-099 |
| 0509 | 20 | | GA | | 30-5 | 33-51-22 | D06396 | 1 | | | SP01358 | | 9 | | 115-199 |
| 0510 | 20 | | GA | | 32-9 | 33-51-22 | D06396 | 2 | | | D00080 | 10 | | | 001-099 |
| 0510 | 20 | | GA | | 32-4 | 33-51-22 | D06396 | 2 | | | D00080 | 13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3530

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3534 | 286N3534 | | | OVERHEAD DISC TO EMERGENCY LIGHTS-LEFT AFT AND MID AFT (continued) | | | | | | | | | | | |
| 0511 | 20 | | GA | | 30-5 | 33-51-22 | D06396 | | 1 | | SP01360 | | 9 | | 001-099 |
| 0511 | 20 | | GA | | 30-5 | 33-51-22 | D06396 | | 3 | | SP01360 | | 9 | | 115-199 |
| 0512 | 20 | | GA | | 2-0 | 33-51-22 | D06396 | | 4 | | GD03716 | DC.. | E | | ALL |
| 0513 | 20 | | GA | | 2-0 | 33-51-22 | D06396 | | 5 | | GD03716 | DC.. | E | | ALL |
| 0514 | 20 | | GA | | 2-0 | 33-51-22 | D06396 | | 6 | | GD03716 | DC.. | E | | ALL |
| 0517 | 22 | | GA | | 17-10 | 33-51-22 | D00080 | | 12 | | D07282 | 1 | VY | | 001-099 |
| 0517 | 22 | | GA | | 14-8 | 33-51-22 | D00080 | | 16 | | D07284 | 1 | VY | | 115-199 |
| 0518 | 20 | | GA | | 6-1 | 33-51-22 | D07310 | | 1 | VG | GD03322 | DC.. | E | | 001-099 |
| 0518 | 20 | | GA | | 4-3 | 33-51-22 | D07312 | | 1 | VG | GD03324 | DC.. | E | | 115-199 |
| 0519 | 22 | | GA | | 23-1 | 33-51-22 | D00076 | | 16 | | D07288 | 1 | VY | | 115-199 |
| 0520 | 20 | | GA | | 7-10 | 33-51-22 | D07314 | | 1 | VG | GD00482 | DC.. | E | | 001-099 |
| 0520 | 20 | | GA | | 4-2 | 33-51-22 | D07316 | | 1 | VG | GD03328 | DC.. | E | | 115-199 |
| W3536 | 286N3536 | | | TO GALLEY LIGHTING AND CONTROL | | | | | | | | | | | |
| 0001 | 20 | | GA | | 12-0 | 33-24-14 | SP02028 | | | 9 | D01940 | | 1 | | 001-099 |
| 0002 | 22 | | GA | | 10-0 | 33-27-31 | D00994 | | 1 | | SP01224 | | 9 | | 001-099 |
| 0002 | 22 | | GA | | 46-0 | 33-27-31 | D00994 | | 1 | | SP00528 | | 9 | | 115-199 |
| 0003 | 22 | | GA | | 8-0 | 33-27-31 | D00994 | | 5 | | D01940 | | 3 | | 001-099 |
| 0003 | 22 | | GA | | 11-0 | 33-27-31 | SP01086 | | | 9 | D00994 | | 5 | | 115-199 |
| 0004 | 22 | | GA | | 136-0 | 25-31-33 | D01940 | | 4 | | D40662P | | 2 | | 001-099 |
| 0004 | 22 | | GA | | 135-0 | 25-31-33 | D01940 | | 4 | | D40662P | | 2 | | 115-199 |
| 0005 | 22 | | GA | | 136-0 | 25-31-33 | D01940 | | 5 | | D40662P | | 3 | | 001-099 |
| 0005 | 22 | | GA | | 135-0 | 25-31-33 | D01940 | | 5 | | D40662P | | 3 | | 115-199 |
| 0006 | 22 | | GA | | 136-0 | 25-31-33 | D01940 | | 6 | | D40662P | | 6 | | 001-099 |
| 0006 | 22 | | GA | | 135-0 | 25-31-33 | D01940 | | 6 | | D40662P | | 6 | | 115-199 |
| 0007 | 20 | | GA | | 136-0 | 25-31-33 | D01940 | | 7 | | D40662P | | 5 | | 001-099 |
| 0007 | 20 | | GA | | 135-0 | 25-31-33 | D01940 | | 7 | | D40662P | | 5 | | 115-199 |
| 0008 | 22 | | GA | | 12-0 | 33-27-31 | D01940 | | 8 | | SP01226 | | 9 | | 001-099 |
| 0010 | 20 | | GA | | 12-0 | 33-24-14 | D01940 | | 2 | | SP02030 | | 9 | | 001-099 |
| 0011 | 22 | | GA | | 8-0 | 33-27-31 | D01940 | | 11 | | D00994 | | 3 | | 001-099 |
| 0011 | 22 | | GA | | 15-0 | 33-27-31 | SP01084 | | | 9 | D00994 | | 3 | | 115-199 |
| 0012 | 20 | | GA | | 12-0 | 33-27-31 | D01940 | | 12 | | SP01228 | | 9 | | 001-099 |
| 0013 | 20 | | GA | | 7-0 | 33-27-31 | D00994 | | 2 | | GD01337 | AC.. | E | | 001-099 |
| 0013 | 20 | | GA | | 5-0 | 33-27-31 | D00994 | | 2 | | GD01337 | AC.. | E | | 115-199 |
| 0015 | 20 | | GA | | 7-0 | 33-27-31 | D00994 | | 4 | | GD01338 | ST.. | E | | 001-099 |
| 0015 | 20 | | GA | | 5-0 | 33-27-31 | D00994 | | 4 | | GD01338 | ST.. | E | | 115-199 |
| 0016 | 20 | | GA | | 12-0 | 33-24-14 | D01940 | | 1 | | SP02028 | | 9 | | 115-199 |
| 0017 | 20 | | GA | | 12-0 | 33-24-14 | D01940 | | 2 | | SP02030 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3530

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Description | | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3538 | 286N3538 | | P31 TO GALLEY NO. 4B AC POWER | | | | | | | | | | | | |
| 0001 | 04 | HA | | 7-2 | 25-31-33 | D01938 | | A | | SM00001 | | GX | | 001-099 | |
| 0001 | 04 | HA | | 5-6 | 25-31-33 | D01938 | | A | | SM00001 | | GX | | 115-199 | |
| 0002 | 04 | HA | | 8-8 | 25-31-33 | D01938 | | B | | SM00002 | | GX | | 001-099 | |
| 0002 | 04 | HA | | 6-0 | 25-31-33 | D01938 | | B | | SM00002 | | GX | | 115-199 | |
| 0003 | 04 | HA | | 9-0 | 25-31-33 | D01938 | | C | | SM00003 | | GX | | 001-099 | |
| 0003 | 04 | HA | | 6-9 | 25-31-33 | D01938 | | C | | SM00003 | | GX | | 115-199 | |
| 0004 | 04 | HA | | 2-0 | 25-31-33 | D01938 | | D | | GD00064 | AC.. | F | | 001-099 | |
| 0004 | 04 | HA | | 3-0 | 25-31-33 | D01938 | | D | | GD00064 | AC.. | F | | 115-199 | |
| 0005 | 02 | 43 | | 134-3 | 25-31-33 | M00227 | | A2 | H2 | SM00001 | | GX | | 001-099 | |
| 0005 | 02 | 43 | | 142-0 | 25-31-33 | M00227 | | A2 | H2 | SM00001 | | GX | | 115-199 | |
| 0006 | 02 | 43 | | 132-9 | 25-31-33 | M00227 | | B2 | H2 | SM00002 | | GX | | 001-099 | |
| 0006 | 02 | 43 | | 142-0 | 25-31-33 | M00227 | | B2 | H2 | SM00002 | | GX | | 115-199 | |
| 0007 | 02 | 43 | | 132-1 | 25-31-33 | M00227 | | C2 | H2 | SM00003 | | GX | | 001-099 | |
| 0007 | 02 | 43 | | 142-0 | 25-31-33 | M00227 | | C2 | H2 | SM00003 | | GX | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W3530

Page 7 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3541 | 286N3541 | | | PASSENGER ADDRESS MUTED SPKR-DR. 1 | | | | | | | | | | | |
| 0001 | 22 | | GA | | 5-5 | 23-31-21 | D01229 | | | | D01227 | 3 | | | ALL |
| 0002 | 22 | | GA | | 5-5 | 23-31-21 | D01229 | | | | D01227 | 7 | | | ALL |
| 2001B | 22 | | GB | AA | 5-5 | 23-31-21 | D01229 | | | | D01227 | 2 | | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 23-31-21 | D01229 | | | | D01227 | 6 | | | ALL |
| 2002B | 22 | | GB | AB | 2-6 | 23-31-21 | B10112 | COM | AC | | SM00001 | | 9 | | ALL |
| 2002R | 22 | | GB | AB | 0-0 | 23-31-21 | B10112 | | 2K | AD | SM00002 | | 9 | | ALL |
| 2003B | 22 | | GB | AC | 6-8 | 23-31-21 | B10111 | COM | AC | | SM00001 | | 9 | | ALL |
| 2003R | 22 | | GB | AC | 0-0 | 23-31-21 | B10111 | | 2K | AD | SM00002 | | 9 | | ALL |
| 2004B | 22 | | GB | AD | 2-6 | 23-31-21 | D01227 | | | | SM00001 | | 9 | | ALL |
| 2004R | 22 | | GB | AD | 0-0 | 23-31-21 | D01227 | | | | SM00002 | | 9 | | ALL |
| W3544 | 286N3544 | | | GALLEY 2D LIGHTING AND CONTROL | | | | | | | | | | | |
| 0007 | 22 | | GA | | 8-0 | 33-27-22 | D04300 | | | | D04332 | 11 | | | 115-199 |
| 0008 | 22 | | GA | | 5-0 | 33-27-22 | D04300 | | | | GD02163 | AC.. | E | | 115-199 |
| 0009 | 22 | | GA | | 8-0 | 33-27-22 | D04300 | | | | D04332 | 3 | | | 115-199 |
| 0010 | 22 | | GA | | 10-0 | 33-27-22 | D04332 | | | 12 | SP01820 | | 9 | | 115-199 |
| 0011 | 22 | | GA | | 10-0 | 33-27-22 | D04332 | | | 8 | SP01822 | | 9 | | 115-199 |
| 0012 | 22 | | GA | | 8-0 | 33-27-22 | D04300 | | | 1 | SP01824 | | 9 | | 115-199 |
| 0013 | 22 | | GA | | 5-0 | 33-27-22 | D04300 | | | 4 | GD02165 | ST.. | E | | 115-199 |
| 0014 | 20 | | GA | | 10-0 | 33-24-12 | D04332 | | | 1 | SP01560 | | 9 | | 115-199 |
| 0015 | 20 | | GA | | 10-0 | 33-24-12 | D04332 | | | 2 | SP01562 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3540

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3562 | 286N3562 | | | GALLEY 2D AC POWER | | | | | | | | | | | |
| 0001 | 12 | | HA | | 42-0 | 25-31-27 | D04330 | | A | | TB5050 | 7 | E | | 115-199 |
| 0002 | 12 | | HA | | 42-0 | 25-31-27 | D04330 | | B | | TB5050 | 8 | E | | 115-199 |
| 0003 | 12 | | HA | | 42-0 | 25-31-27 | D04330 | | C | | TB5050 | 9 | E | | 115-199 |
| 0004 | 12 | | HA | | 3-0 | 25-31-27 | D04330 | | D | | GD00332 | AC.L | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3560

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3570 | 286N3570 | | | | JUMPER BUNDLE,ATTENDANT PNL LEFT TO RIGHT AND ENTRY LIGHTS | | | | | | | | | | | | |
| 0001 | 22 | | GA | | 17-0 | 33-22-12 | | D52172P | 1 | | | D04788 | 1 | | | 115-199 | |
| 0002 | 22 | | GA | | 15-0 | 33-22-12 | | D04788 | 2 | | | SM00001 | | 9 | | 115-199 | |
| 0003 | 20 | | GA | | 17-0 | 33-22-12 | | D52172P | 3 | | | D04788 | 3 | | | 115-199 | |
| 0004 | 22 | | GA | | 7-0 | 33-22-12 | | L00252 | =P | C | | SM00001 | | 9 | | 115-199 | |
| 0005 | 20 | | GA | | 10-0 | 33-22-12 | | L00252 | =G | C | | GD01479 | AC.. | E | | 115-199 | |
| 0006 | 22 | | GA | | 14-0 | 33-22-12 | | L00253 | =P | C | | SM00001 | | 9 | | 115-199 | |
| 0007 | 20 | | GA | | 2-0 | 33-22-12 | | L00253 | =G | C | | GD01480 | AC.. | E | | 115-199 | |
| W3572 | 286N3572 | | | | MISC. LIGHTING LEFT | | | | | | | | | | | | |
| 0018 | 22 | | GA | | 11-0 | 33-26-31 | | L00586 | =P | C | | SM00016 | | 9 | | 001-099 | |
| 0019 | 20 | | GA | | 9-0 | 33-26-31 | | L00586 | =G | C | | GD02605 | AC.. | E | | 001-008 | |
| 0019 | 20 | | GA | | 10-0 | 33-26-31 | | L00586 | =G | C | | GD02605 | AC.. | E | | 009-099 | |
| 0033 | 16 | | GA | | 38-0 | 33-26-11 | | D40496P | 3 | 16 | | SM00003 | | 9 | | 001-099 | |
| 0033 | 22 | | GA | | 39-0 | 33-26-11 | | D40496P | 3 | | | SM00003 | | 9 | | 115-199 | |
| 0034 | 22 | | GA | | 11-0 | 33-26-11 | | D00042 | 16 | | | SM00004 | | 9 | | 001-099 | |
| 0034 | 22 | | GA | | 12-0 | 33-26-11 | | D00042 | 16 | | | SM00004 | | 9 | | 115-199 | |
| 0035 | 22 | | GA | | 11-0 | 33-26-11 | | D00042 | 6 | | | SM00005 | | 9 | | 001-099 | |
| 0035 | 22 | | GA | | 12-0 | 33-26-11 | | D00042 | 6 | | | SM00005 | | 9 | | 115-199 | |
| 0036 | 22 | | GA | | 38-0 | 33-26-11 | | D40496P | 4 | | | SM00004 | | 9 | | 001-099 | |
| 0036 | 22 | | GA | | 39-0 | 33-26-11 | | D40496P | 4 | | | SM00004 | | 9 | | 115-199 | |
| 0037 | 22 | | GA | | 38-0 | 33-26-11 | | D40496P | 7 | | | SM00005 | | 9 | | 001-099 | |
| 0037 | 22 | | GA | | 39-0 | 33-26-11 | | D40496P | 7 | | | SM00005 | | 9 | | 115-199 | |
| 0038 | 16 | | GA | | 11-0 | 33-26-11 | | D00042 | 18 | 16 | | SM00003 | | 9 | | 001-099 | |
| 0038 | 22 | | GA | | 12-0 | 33-26-11 | | D00042 | 18 | | | SM00003 | | 9 | | 115-199 | |
| 0039 | 18 | | GA | | 4-0 | 33-26-11 | | D00042 | 39 | | | GD02884 | AC.. | E | | 001-099 | |
| 0039 | 18 | | GA | | 5-0 | 33-26-11 | | D00042 | 39 | | | GD02884 | AC.. | E | | 115-199 | |
| 0040 | 18 | | GA | | 5-0 | 33-26-11 | | D00042 | 40 | | | GD01468 | AC.. | E | | ALL | |
| 0041 | 16 | | GA | | 4-0 | 33-26-11 | | D00042 | 1 | | | GD01469 | ST.. | E | | 001-099 | |
| 0041 | 16 | | GA | | 5-0 | 33-26-11 | | D00042 | 1 | | | GD01469 | ST.. | E | | 115-199 | |
| 0042 | 22 | | GA | | 74-0 | 33-26-11 | | D00044 | 16 | | | SM00004 | | 9 | | 001-099 | |
| 0043 | 22 | | GA | | 74-0 | 33-26-11 | | D00044 | 6 | | | SM00005 | | 9 | | 001-099 | |
| 0044 | 16 | | GA | | 74-0 | 33-26-11 | | D00044 | 18 | 16 | | SM00003 | | 9 | | 001-099 | |
| 0045 | 16 | | GA | | 6-0 | 33-26-11 | | D00044 | 1 | | | GD01483 | ST.. | E | | 001-099 | |
| 0046 | 18 | | GA | | 7-0 | 33-26-11 | | D00044 | 39 | | | GD02886 | AC.. | E | | 001-099 | |
| 0047 | 18 | | GA | | 6-0 | 33-26-11 | | D00044 | 40 | | | GD01482 | AC.. | E | | 001-099 | |
| 0048 | 16 | | GA | | 38-0 | 33-26-21 | | D40496P | 12 | 16 | | SM00006 | | 9 | | 001-099 | |
| 0048 | 22 | | GA | | 39-0 | 33-26-21 | | D40496P | 12 | | | SM00006 | | 9 | | 115-199 | |
| 0050 | 16 | | GA | | 11-0 | 33-26-21 | | D00042 | 3 | 16 | | SM00006 | | 9 | | 001-099 | |
| 0050 | 22 | | GA | | 12-0 | 33-26-21 | | D00042 | 3 | | | SM00006 | | 9 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|---------|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3572 | 286N3572 | MISC. LIGHTING LEFT (continued) | | | | | | | | | | | | | |
| 0053 | 16 | GA | 13-0 | 33-26-21 | L00418 | LAV | C | | SM00006 | | | 9 | | 001-099 | |
| 0053 | 22 | GA | 12-0 | 33-26-21 | L00643 | LAV | C | | SM00006 | | | 9 | | 115-199 | |
| 0054 | 16 | GA | 8-0 | 33-26-21 | L00418 | GND | C | | GD01472 | AC.. | E | | | 001-099 | |
| 0054 | 20 | GA | 18-0 | 33-26-21 | L00643 | GND | C | | GD01472 | AC.. | E | | | 115-199 | |
| 0055 | 16 | GA | 7-0 | 33-26-21 | D00044 | | 4 | 16 | SP00550 | | | 9 | | 001-099 | |
| 0056 | 16 | GA | 74-0 | 33-26-21 | D00044 | | 3 | 16 | SM00006 | | | 9 | | 001-099 | |
| 0059 | 22 | GA | 50-0 | 33-26-31 | D40496P | | 23 | | L00352 | =P | C | | | 001-099 | |
| 0059 | 22 | GA | 54-0 | 33-26-31 | D40496P | | 26 | | L00352 | =P | C | | | 115-199 | |
| 0060 | 22 | GA | 51-0 | 33-26-31 | L00353 | CAP | Y | | SM00016 | | | 9 | | 001-099 | |
| 0060 | 22 | GA | 39-0 | 33-26-31 | D40496P | | 22 | | SM00011 | | | 9 | | 115-199 | |
| 0061 | 20 | GA | 2-0 | 33-26-31 | L00352 | =G | C | | GD01465 | AC.. | E | | | 001-099 | |
| 0061 | 20 | GA | 3-0 | 33-26-31 | L00352 | =G | C | | GD01465 | AC.. | E | | | 115-199 | |
| 0062 | 20 | GA | 3-0 | 33-26-31 | L00353 | CAP | Y | | GD01486 | AC.. | E | | | 001-099 | |
| 0062 | 20 | GA | 10-0 | 33-26-31 | L00480 | =G | C | | GD01833 | AC.. | E | | | 115-199 | |
| 0063 | 22 | GA | 90-0 | 33-27-31 | D40496P | | 9 | | SP00532 | | | 9 | | 115-199 | |
| 0064 | 22 | GA | 90-0 | 33-27-31 | D40496P | | 10 | | SP00530 | | | 9 | | 115-199 | |
| 0065 | 22 | GA | 90-0 | 33-27-31 | D40496P | | 11 | | SP00528 | | | 9 | | 115-199 | |
| 0067 | 22 | GA | 46-0 | 38-13-11 | D40496P | | 16 | | D00042 | | 38 | | | 001-099 | |
| 0067 | 18 | GA | 48-0 | 38-13-11 | D40496P | | 23 | 18 | D00042 | | 38 | | | 115-199 | |
| 0070 | 24 | GK | 9-0 | 38-32-11 | D41120J | | 1 | | D00042 | | 34 | | | 001-099 | |
| 0070 | 20 | GA | 9-0 | 38-32-11 | D41120J | | 1 | | D00042 | | 34 | | | 115-199 | |
| 0071 | 24 | GK | 9-0 | 38-32-11 | D41120J | | 2 | | D00042 | | 35 | | | 001-099 | |
| 0071 | 20 | GA | 9-0 | 38-32-11 | D41120J | | 2 | | D00042 | | 35 | | | 115-199 | |
| 0072 | 24 | GK | 9-0 | 38-32-11 | D41120J | | 3 | | D00042 | | 36 | | | 001-099 | |
| 0072 | 20 | GA | 9-0 | 38-32-11 | D41120J | | 3 | | D00042 | | 36 | | | 115-199 | |
| 0073 | 24 | GK | 76-0 | 38-32-11 | D41120J | | 11 | | D00044 | | 34 | | | 001-099 | |
| 0074 | 24 | GK | 76-0 | 38-32-11 | D41120J | | 12 | | D00044 | | 35 | | | 001-099 | |
| 0075 | 24 | GK | 76-0 | 38-32-11 | D41120J | | 13 | | D00044 | | 36 | | | 001-099 | |
| 0076 | 18 | GA | 5-0 | 38-32-11 | D00042 | | 37 | | GD01468 | AC.. | E | | | 001-099 | |
| 0077 | 18 | GA | 6-0 | 38-32-11 | D00044 | | 37 | | GD01482 | AC.. | E | | | 001-099 | |
| 0078 | 22 | GA | 38-0 | 38-32-21 | D40496P | | 8 | | SM00007 | | | 9 | | 001-099 | |
| 0078 | 20 | GA | 39-0 | 38-32-21 | D40496P | | 27 | | SM00007 | | | 9 | | 115-199 | |
| 0079 | 22 | GA | 11-0 | 38-32-21 | D00042 | | 19 | | SM00007 | | | 9 | | 001-099 | |
| 0079 | 20 | GA | 12-0 | 38-32-21 | D00042 | | 19 | | SM00007 | | | 9 | | 115-199 | |
| 0080 | 24 | GK | 11-0 | 38-32-21 | D00042 | | 20 | | SM00008 | | | 9 | | 001-099 | |
| 0080 | 20 | GA | 12-0 | 38-32-21 | D00042 | | 20 | | SM00008 | | | 9 | | 115-199 | |
| 0081 | 20 | GA | 4-0 | 38-32-21 | D00042 | | 22 | | GD01467 | DC.. | E | | | 001-099 | |
| 0081 | 18 | GA | 5-0 | 38-32-21 | D00042 | | 22 | | GD01467 | DC.. | E | | | 115-199 | |
| 0082 | 22 | GA | 74-0 | 38-32-21 | D00044 | | 19 | | SM00007 | | | 9 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3572 | 286N3572 | | | MISC. LIGHTING LEFT (continued) | | | | | | | | | | | |
| 0083 | 24 | | GK | | 74-0 | 38-32-21 | D00044 | 20 | | | SM00008 | | 9 | | 001-099 |
| 0084 | 24 | | GK | | 38-0 | 38-32-21 | D40496P | 2 | | | SM00008 | | 9 | | 001-099 |
| 0085 | 20 | | GA | | 6-0 | 38-32-21 | D00044 | 22 | | | GD01481 | DC.. | E | | 001-099 |
| 0086 | 22 | | GA | | 9-0 | 33-14-41 | D41120J | 7 | | | D00042 | 23 | | | ALL |
| 0087 | 20 | | GA | | 5-0 | 35-21-12 | D41548P | 11 | | | D00042 | 11 | | | 001-099 |
| 0087 | 20 | | GA | | 6-0 | 35-21-12 | D41548P | 11 | | | D00042 | 11 | | | 115-199 |
| 0088 | 20 | | GA | | 4-0 | 35-21-13 | D00044 | 11 | | | D03460 | 11 | | | 001-099 |
| 0089 | 20 | | GA | | 27-0 | SPARE | D41120J | CAP | Y | | D05690 | 12 | | | 001-099 |
| 0089 | 20 | | GA | | 7-0 | SPARE | D41120J | 10 | | | D00044 | 12 | | | 115-199 |
| 0090 | 20 | | GA | | 46-0 | SPARE | D40496P | 5 | | | D00042 | 25 | | | 001-099 |
| 0090 | 20 | | GA | | 48-0 | SPARE | D40496P | 5 | | | D00042 | 25 | | | 115-199 |
| 0091 | 20 | | GA | | 46-0 | SPARE | D40496P | 6 | | | D00042 | 26 | | | 001-099 |
| 0091 | 20 | | GA | | 48-0 | SPARE | D40496P | 6 | | | D00042 | 26 | | | 115-199 |
| 0092 | 20 | | GA | | 43-0 | SPARE | D40496P | 13 | | | D05690 | 25 | | | 001-099 |
| 0092 | 20 | | GA | | 46-0 | SPARE | D40496P | 13 | | | D00044 | 25 | | | 115-199 |
| 0093 | 20 | | GA | | 92-0 | 38-13-11 | D40496P | 21 | | | D00044 | 38 | | | 001-099 |
| 0093 | 20 | | GA | | 46-0 | SPARE | D40496P | 14 | | | D00044 | 26 | | | 115-199 |
| 0105 | 22 | | GA | | 5-0 | 33-25-11 | D00042 | 2 | | | D41548P | 2 | | | 001-099 |
| 0105 | 22 | | GA | | 6-0 | 33-25-11 | D00042 | 2 | | | D41548P | 9 | | | 115-199 |
| 0106 | 22 | | GA | | 5-0 | 33-25-11 | D00042 | 5 | | | D41548P | 5 | | | 001-099 |
| 0106 | 22 | | GA | | 6-0 | 33-25-11 | D00042 | 5 | | | D41548P | 5 | | | 115-199 |
| 0107 | 22 | | GA | | 7-0 | 33-25-11 | D00042 | 17 | | | SP00536 | | 9 | | ALL |
| 0108 | 18 | | GA | | 5-0 | 35-21-12 | D00042 | 15 | | | D41548P | 10 | | | 001-099 |
| 0108 | 18 | | GA | | 6-0 | 35-21-12 | D00042 | 15 | | | D41548P | 10 | | | 115-199 |
| 0109 | 22 | | GA | | 9-0 | 33-25-11 | D41548P | 4 | | | SP00534 | | 9 | | 001-099 |
| 0109 | 22 | | GA | | 8-0 | 33-25-11 | D41548P | 4 | | | SP00534 | | 9 | | 115-199 |
| 0111 | 20 | | GA | | 38-0 | 33-24-11 | D40496P | 17 | | | SM00009 | | 9 | | 001-099 |
| 0111 | 18 | | GA | | 39-0 | 33-24-11 | D40496P | 31 | 18 | | SM00009 | | 9 | | 115-199 |
| 0112 | 18 | | GA | | 39-0 | 33-24-11 | D40496P | 30 | 18 | | SM00010 | | 9 | | 115-199 |
| 0113 | 20 | | GA | | 11-0 | 33-24-11 | D00042 | 7 | | | SM00009 | | 9 | | 001-099 |
| 0113 | 18 | | GA | | 12-0 | 33-24-11 | D00042 | 7 | 18 | | SM00009 | | 9 | | 115-199 |
| 0114 | 20 | | GA | | 4-0 | 33-24-11 | D00042 | 8 | | | GD02884 | AC.. | E | | 001-099 |
| 0114 | 18 | | GA | | 12-0 | 33-24-11 | D00042 | 8 | 18 | | SM00010 | | 9 | | 115-199 |
| 0115 | 18 | | GA | | 10-0 | 33-24-11 | D00044 | 7 | 18 | | SM00009 | | 9 | | 115-199 |
| 0116 | 18 | | GA | | 10-0 | 33-24-11 | D00044 | 8 | 18 | | SM00010 | | 9 | | 115-199 |
| 0117 | 22 | | GA | | 7-0 | 33-25-14 | D00044 | 17 | | | SP00546 | | 9 | | 001-099 |
| 0118 | 22 | | GA | | 4-0 | 33-25-14 | D00044 | 2 | | | D03460 | 2 | | | 001-099 |
| 0119 | 22 | | GA | | 4-0 | 33-25-14 | D00044 | 5 | | | D03460 | 5 | | | 001-099 |
| 0120 | 18 | | GA | | 4-0 | 35-21-13 | D00044 | 15 | | | D03460 | 10 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3572 | | 286N3572 | | | | MISC. LIGHTING LEFT (continued) | | | | | | | | | |
| 0121 | 16 | GA | | | 4-0 | 38-32-11 | D00042 | 30 | | | GD01469 | ST.. | E | | 001-099 |
| 0121 | 16 | GA | | | 5-0 | 38-32-11 | D00042 | 30 | | | GD01469 | ST.. | E | | 115-199 |
| 0122 | 16 | GA | | | 6-0 | 38-32-11 | D00044 | 30 | | | GD01483 | ST.. | E | | 001-099 |
| 0123 | 20 | GA | | | 10-0 | 33-25-21 | D41120J | 8 | | | SP00006 | | 9 | | 001-099 |
| 0123 | 22 | GA | | | 12-0 | 33-26-31 | L00480 | =P | C | | SM00011 | | 9 | | 115-199 |
| 0124 | 22 | GA | | | 31-0 | 33-26-31 | L00523 | CAP | Y | | SM00011 | | 9 | | 115-199 |
| 0125 | 16 | GA | | | 12-0 | 33-26-21 | L00418 | OCC | C | | D00042 | 4 | 16 | | 001-099 |
| 0125 | 20 | GA | | | 3-0 | 33-26-31 | L00523 | CAP | Y | | GD01837 | AC.. | E | | 115-199 |
| 0126 | 22 | GA | | | 43-0 | 33-26-31 | D40496P | 19 | | | SM00016 | | 9 | | 001-099 |
| 0128 | 22 | GA | | | 43-0 | 38-13-11 | D40496P | 14 | | | D05690 | 38 | | | 001-099 |
| 0129 | 24 | GK | | | 27-0 | 38-32-11 | D41120J | 4 | | | D05690 | 34 | | | 001-099 |
| 0130 | 24 | GK | | | 27-0 | 38-32-11 | D41120J | 5 | | | D05690 | 35 | | | 001-099 |
| 0131 | 24 | GK | | | 27-0 | 38-32-11 | D41120J | 6 | | | D05690 | 36 | | | 001-099 |
| 0132 | 18 | GA | | | 5-0 | 38-32-11 | D05690 | 37 | | | GD02666 | AC.. | E | | 001-099 |
| 0133 | 22 | GA | | | 24-0 | 38-32-21 | D05690 | 19 | | | SM00007 | | 9 | | 001-099 |
| 0134 | 24 | GK | | | 24-0 | 38-32-21 | D05690 | 20 | | | SM00008 | | 9 | | 001-099 |
| 0135 | 20 | GA | | | 5-0 | 38-32-21 | D05690 | 22 | | | GD02706 | DC.. | E | | 001-099 |
| 0137 | 20 | GA | | | 74-0 | 33-24-11 | D00044 | 7 | | | SM00009 | | 9 | | 001-099 |
| 0138 | 20 | GA | | | 4-0 | 33-24-11 | D00044 | 8 | | | GD03348 | AC.. | E | | 001-099 |
| 0143 | 16 | GA | | | 5-0 | 38-32-11 | D05690 | 30 | | | GD02680 | ST.. | E | | 001-099 |
| 0145 | 22 | GA | | | 24-0 | 33-26-11 | D05690 | 16 | | | SM00004 | | 9 | | 001-099 |
| 0146 | 22 | GA | | | 24-0 | 33-26-11 | D05690 | 6 | | | SM00005 | | 9 | | 001-099 |
| 0147 | 16 | GA | | | 24-0 | 33-26-11 | D05690 | 18 | 16 | | SM00003 | | 9 | | 001-099 |
| 0148 | 16 | GA | | | 5-0 | 33-26-11 | D05690 | 1 | | | GD02680 | ST.. | E | | 001-099 |
| 0149 | 18 | GA | | | 5-0 | 33-26-11 | D05690 | 39 | | | GD02616 | AC.. | E | | 001-008 |
| 0149 | 18 | GA | | | 6-0 | 33-26-11 | D05690 | 39 | | | GD02616 | AC.. | E | | 009-099 |
| 0150 | 18 | GA | | | 5-0 | 33-26-11 | D05690 | 40 | | | GD02666 | AC.. | E | | 001-099 |
| 0150 | 22 | GA | | | 10-0 | 33-26-11 | D00044 | 16 | | | SM00004 | | 9 | | 115-199 |
| 0151 | 20 | GA | | | 9-0 | SPARE | D41120J | CAP | Y | | D00042 | CAP | Y | | 001-099 |
| 0151 | 22 | GA | | | 10-0 | 33-26-11 | D00044 | 6 | | | SM00005 | | 9 | | 115-199 |
| 0152 | 20 | GA | | | 5-0 | 33-24-12 | D00042 | 10 | | | D41548P | 1 | | | 001-099 |
| 0152 | 22 | GA | | | 10-0 | 33-26-11 | D00044 | 18 | | | SM00003 | | 9 | | 115-199 |
| 0153 | 16 | GA | | | 3-0 | 33-26-11 | D00044 | 1 | | | GD02178 | ST.. | E | | 115-199 |
| 0154 | 18 | GA | | | 3-0 | 33-26-11 | D00044 | 39 | | | GD02892 | AC.. | E | | 115-199 |
| 0155 | 20 | GA | | | 46-0 | SPARE | D00042 | 12 | | | D40496P | 15 | | | 001-099 |
| 0155 | 18 | GA | | | 3-0 | 33-26-11 | D00044 | 40 | | | GD02177 | AC.. | E | | 115-199 |
| 0156 | 22 | GA | | | 14-0 | 33-26-21 | D00044 | 4 | | | L00643 | OCC | C | | 115-199 |
| 0157 | 20 | GA | | | 5-0 | 33-24-12 | D00042 | 9 | | | D41548P | 7 | | | 001-099 |
| 0157 | 22 | GA | | | 10-0 | 33-26-21 | D00044 | 3 | | | D00042 | 4 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3572 | 286N3572 | | | | MISC. LIGHTING LEFT (continued) | | | | | | | | | | | |
| 0158 | 18 | | GA | | 46-0 | 38-13-11 | | D40496P | 21 | 18 | | D00044 | 38 | | | 115-199 |
| 0159 | 18 | | GA | | 7-0 | 38-32-11 | | D41120J | 4 | | | D00044 | 34 | | | 115-199 |
| 0160 | 18 | | GA | | 7-0 | 38-32-11 | | D41120J | 5 | | | D00044 | 35 | | | 115-199 |
| 0161 | 18 | | GA | | 7-0 | 38-32-11 | | D41120J | 6 | | | D00044 | 36 | | | 115-199 |
| 0162 | 18 | | GA | | 5-0 | 38-32-11 | | D00042 | 37 | | | GD01468 | AC.. | E | | 115-199 |
| 0163 | 16 | | GA | | 24-0 | 33-26-21 | | D05690 | 3 | 16 | | SM00006 | | 9 | | 001-099 |
| 0163 | 18 | | GA | | 3-0 | 38-32-11 | | D00044 | 37 | | | GD02177 | AC.. | E | | 115-199 |
| 0164 | 24 | | GK | | 10-0 | 24-51-71 | | D41104P | 1 | | | D40496P | 1 | | | 001-099 |
| 0164 | 20 | | GA | | 10-0 | 38-32-21 | | D00044 | 19 | | | SM00007 | | 9 | | 115-199 |
| 0165 | 24 | | GK | | 10-0 | 24-51-71 | | D41104P | 2 | | | D40496P | 20 | | | 001-099 |
| 0165 | 20 | | GA | | 10-0 | 38-32-21 | | D00044 | 20 | | | SM00008 | | 9 | | 115-199 |
| 0166 | 20 | | GA | | 45-0 | SPARE | | D41104P | 3 | | | D41120J | 9 | | | 001-099 |
| 0166 | 20 | | GA | | 39-0 | 38-32-21 | | D40496P | 2 | | | SM00008 | | 9 | | 115-199 |
| 0167 | 18 | | GA | | 45-0 | 25-31-33 | | D41104P | 4 | | | D41120J | 10 | | | 001-099 |
| 0167 | 18 | | GA | | 3-0 | 38-32-21 | | D00044 | 22 | | | GD02179 | DC.. | E | | 115-199 |
| 0168 | 22 | | GA | | 7-0 | 33-25-11 | | D00044 | 17 | | | SP00536 | | 9 | | 115-199 |
| 0169 | 22 | | GA | | 7-0 | 33-25-11 | | D00044 | 2 | | | D04626 | 9 | | | 115-199 |
| 0170 | 22 | | GA | | 17-0 | 33-25-11 | | D05690 | 17 | | | SP01248 | | 9 | | 001-099 |
| 0170 | 22 | | GA | | 7-0 | 33-25-11 | | D00044 | 5 | | | D04626 | 5 | | | 115-199 |
| 0171 | 22 | | GA | | 7-0 | 33-25-11 | | D05690 | 2 | | | D05896 | 2 | | | 001-008 |
| 0171 | 22 | | GA | | 7-0 | 33-25-11 | | D05690 | 2 | | | D41498P | 2 | | | 009-099 |
| 0171 | 18 | | GA | | 7-0 | 35-21-12 | | D00044 | 15 | | | D04626 | 10 | | | 115-199 |
| 0172 | 22 | | GA | | 7-0 | 33-25-11 | | D05690 | 5 | | | D05896 | 5 | | | 001-008 |
| 0172 | 22 | | GA | | 7-0 | 33-25-11 | | D05690 | 5 | | | D41498P | 5 | | | 009-099 |
| 0172 | 16 | | GA | | 3-0 | 38-32-11 | | D00044 | 30 | | | GD02178 | ST.. | E | | 115-199 |
| 0173 | 18 | | GA | | 7-0 | 35-21-12 | | D05690 | 15 | | | D05896 | 10 | | | 001-008 |
| 0173 | 18 | | GA | | 7-0 | 35-21-12 | | D05690 | 15 | | | D41498P | 10 | | | 009-099 |
| 0173 | 20 | | GA | | 7-0 | 35-21-12 | | D04626 | 11 | | | D00044 | 11 | | | 115-199 |
| 0174 | 20 | | GA | | 7-0 | 35-21-12 | | D05690 | 11 | | | D05896 | 11 | | | 001-008 |
| 0174 | 20 | | GA | | 7-0 | 35-21-12 | | D05690 | 11 | | | D41498P | 11 | | | 009-099 |
| 0174 | 20 | | GA | | 7-0 | 33-24-12 | | D00044 | 9 | | | D04626 | 7 | | | 115-199 |
| 0175 | 20 | | GA | | 7-0 | SPARE | | D05690 | 9 | | | D05896 | 7 | | | 001-008 |
| 0175 | 20 | | GA | | 7-0 | SPARE | | D05690 | 9 | | | D41498P | 7 | | | 009-099 |
| 0175 | 20 | | GA | | 7-0 | 33-24-12 | | D00044 | 10 | | | D04626 | 1 | | | 115-199 |
| 0176 | 20 | | GA | | 7-0 | SPARE | | D05690 | 10 | | | D05896 | 1 | | | 001-008 |
| 0176 | 20 | | GA | | 7-0 | SPARE | | D05690 | 10 | | | D41498P | 1 | | | 009-099 |
| 0176 | 20 | | GA | | 11-0 | 33-25-21 | | D41120J | 8 | | | SP00006 | | 9 | | 115-199 |
| 0177 | 24 | | GK | | 45-0 | SPARE | | D40496P | 18 | | | SP01266 | | 9 | | 001-099 |
| 0195 | 20 | | GA | | 5-0 | 33-24-11 | | D05690 | 8 | | | GD02616 | AC.. | E | | 001-008 |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3572 | 286N3572 | | | MISC. LIGHTING LEFT (continued) | | | | | | | | | | | |
| 0195 | 20 | | GA | | 6-0 | 33-24-11 | D05690 | | 8 | | GD02616 | AC.. | E | | 009-099 |
| 0196 | 20 | | GA | | 24-0 | 33-24-11 | D05690 | | 7 | | SM00009 | | 9 | | 001-099 |
| 2001B | 22 | | GB | AA | 5-0 | 23-31-21 | D00042 | | 13 | | D41548P | | 14 | | 001-099 |
| 2001R | 22 | | GB | AA | 0-0 | 23-31-21 | D00042 | | 14 | | D41548P | | 13 | | 001-099 |
| 2002B | 22 | | GB | AB | 4-0 | 23-31-22 | D00044 | | 13 | | D03460 | | 14 | | 001-099 |
| 2002R | 22 | | GB | AB | 0-0 | 23-31-22 | D00044 | | 14 | | D03460 | | 13 | | 001-099 |
| 2003B | 22 | | GB | AA | 6-0 | 23-31-21 | D00042 | | 13 | | D41548P | | 13 | | 115-199 |
| 2003R | 22 | | GB | AA | 0-0 | 23-31-21 | D00042 | | 14 | | D41548P | | 14 | | 115-199 |
| 2004B | 22 | | GB | AB | 7-0 | 23-31-21 | D00044 | | 13 | | D04626 | | 13 | | 115-199 |
| 2004R | 22 | | GB | AB | 0-0 | 23-31-21 | D00044 | | 14 | | D04626 | | 14 | | 115-199 |
| 2005B | 22 | | GB | AC | 7-0 | 23-31-21 | D05690 | | 13 | | D05896 | | 14 | | 001-008 |
| 2005B | 22 | | GB | AC | 7-0 | 23-31-21 | D05690 | | 13 | | D41498P | | 14 | | 009-099 |
| 2005R | 22 | | GB | AC | 0-0 | 23-31-21 | D05690 | | 14 | | D05896 | | 13 | | 001-008 |
| 2005R | 22 | | GB | AC | 0-0 | 23-31-21 | D05690 | | 14 | | D41498P | | 13 | | 009-099 |
| W3574 | 286N3574 | | | JUMPER BUNDLE (LAV B PROVISIONS) | | | | | | | | | | | |
| 0001 | 16 | | GA | | 2-0 | SPARE | D07656 | | 28 | | D07656 | | 29 | | 001-099 |
| 0002 | 16 | | GA | | 2-0 | SPARE | D07656 | | 31 | | D07656 | | 32 | | 001-099 |
| 0003 | 16 | | GA | | 2-0 | SPARE | D07656 | | 33 | | D07656 | | 41 | | 001-099 |
| 0004 | 16 | | GA | | 2-0 | SPARE | D07656 | | 42 | | D07656 | | 43 | | 001-099 |
| 0005 | 16 | | GA | | 2-0 | 33-26-21 | D07656 | | 3 | 16 | D07656 | | 4 | 16 | 001-099 |
| W3576 | 286N3576 | | | P34 TO P21, P22 ATTENDANT PANELS | | | | | | | | | | | |
| 0001 | 20 | | GA | | 51-0 | 33-22-11 | D40882J | | 1 | | D41474P | | 1 | | 001-099 |
| 0001 | 20 | | GA | | 49-0 | 33-22-11 | D03456 | | 1 | | D41474P | | 1 | | 115-199 |
| 0002 | 22 | | GA | | 49-0 | 33-22-11 | D41474P | | 31 | | L00259 | =P | C | | 001-099 |
| 0002 | 22 | | GA | | 51-0 | 33-22-11 | D41474P | | 31 | | L00259 | =P | C | | 115-199 |
| 0003 | 22 | | GA | | 15-0 | 33-22-11 | D40882J | | 3 | | L00260 | =P | C | | 001-099 |
| 0003 | 22 | | GA | | 4-0 | 33-22-11 | D03456 | | 3 | | L00260 | =P | C | | 115-199 |
| 0004 | 20 | | GA | | 2-0 | 33-22-11 | D40882J | | 4 | | GD03406 | AC.. | E | | 001-099 |
| 0004 | 20 | | GA | | 3-0 | 33-22-11 | D03456 | | 4 | | GD01471 | AC.. | E | | 115-199 |
| 0005 | 22 | | GA | | 35-0 | 33-22-11 | SP01312 | | | 9 | D41474P | | 5 | | 001-099 |
| 0005 | 22 | | GA | | 49-0 | 33-22-11 | D03456 | | 5 | | D41474P | | 5 | | 115-199 |
| 0006 | 22 | | GA | | 35-0 | 33-22-11 | SP01314 | | | 9 | D41474P | | 6 | | 001-099 |
| 0006 | 22 | | GA | | 49-0 | 33-22-11 | D03456 | | 6 | | D41474P | | 6 | | 115-199 |
| 0007 | 22 | | GA | | 15-0 | 33-22-11 | D40882J | | 7 | | D03438 | | 3 | | 001-099 |
| 0007 | 22 | | GA | | 5-0 | 33-22-11 | D03456 | | 7 | | D03438 | | 3 | | 115-199 |
| 0008 | 22 | | GA | | 8-0 | 33-22-11 | D40882J | | 8 | | SM00001 | | | 9 | 001-099 |
| 0008 | 22 | | GA | | 3-0 | 33-22-11 | D03456 | | 8 | | SM00001 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3576 | 286N3576 | | | | P34 TO P21, P22 ATTENDANT PANELS (continued) | | | | | | | | | | | | |
| 0009 | 20 | | GA | | 3-0 | 33-22-11 | L00260 | =G | | C | | GD01466 | AC.. | E | | 001-099 | |
| 0009 | 20 | | GA | | 4-0 | 33-22-11 | L00260 | =G | | C | | GD01466 | AC.. | E | | 115-199 | |
| 0010 | 20 | | GA | | 3-0 | 33-22-11 | L00259 | =G | | C | | GD01473 | AC.. | E | | 001-099 | |
| 0010 | 20 | | GA | | 4-0 | 33-22-11 | L00259 | =G | | C | | GD01473 | AC.. | E | | 115-199 | |
| 0011 | 22 | | GA | | 35-0 | 33-22-11 | SP01316 | | | 9 | | D41474P | 3 | | | 001-099 | |
| 0011 | 22 | | GA | | 50-0 | 33-22-11 | D03438 | | 1 | | | D41474P | 3 | | | 115-199 | |
| 0012 | 22 | | GA | | 45-0 | 33-22-11 | D41474P | | 8 | | | SM00001 | | 9 | | 001-099 | |
| 0012 | 22 | | GA | | 46-0 | 33-22-11 | D41474P | | 8 | | | SM00001 | | 9 | | 115-199 | |
| 0013 | 22 | | GA | | 9-0 | 33-22-11 | D03438 | | 5 | | | SM00001 | | 9 | | 001-099 | |
| 0013 | 22 | | GA | | 4-0 | 33-22-11 | D03438 | | 5 | | | SM00001 | | 9 | | 115-199 | |
| 0014 | 20 | | GA | | 4-0 | 33-22-11 | D03438 | | 2 | | | GD01468 | AC.. | E | | 001-099 | |
| 0014 | 20 | | GA | | 3-0 | 33-22-11 | D03438 | | 2 | | | GD01468 | AC.. | E | | 115-199 | |
| 0016 | 20 | | GA | | 4-0 | 33-22-11 | D03438 | | 4 | | | GD01469 | ST.. | E | | 001-099 | |
| 0016 | 20 | | GA | | 3-0 | 33-22-11 | D03438 | | 4 | | | GD01469 | ST.. | E | | 115-199 | |
| 0017 | 22 | | GA | | 51-0 | 33-22-12 | D07612 | | 1 | | | D41474P | 2 | | | 001-099 | |
| 0017 | 22 | | GA | | 49-0 | 33-22-12 | D42172J | | 1 | | | D41474P | 2 | | | 115-199 | |
| 0020 | 22 | | GA | | 55-0 | 33-22-12 | D41474P | | 29 | | | SP01160 | | 9 | | 115-199 | |
| 0024 | 22 | | GA | | 14-0 | 33-22-12 | D07612 | | 2 | | | L00253 | =P | C | | 001-099 | |
| 0025 | 20 | | GA | | 5-0 | 33-22-12 | L00253 | =G | | C | | GD01480 | AC.. | E | | 001-099 | |
| 0026 | 20 | | GA | | 7-0 | 33-22-12 | SP01162 | | | 9 | | GD01443 | AC.. | E | | 115-199 | |
| 0027 | 22 | | GA | | 37-0 | 23-34-15 | D40882J | | 32 | | | D41702J | 1 | | | 001-099 | |
| 0027 | 22 | | GA | | 35-0 | 23-34-15 | D41702J | | 1 | | | D03456 | 32 | | | 115-199 | |
| 0028 | 20 | | GA | | 3-0 | 23-34-15 | D40882J | | 33 | | | GD03402 | DC.. | E | | 001-099 | |
| 0028 | 20 | | GA | | 3-0 | 23-34-15 | D03456 | | 33 | | | GD01471 | AC.. | E | | 115-199 | |
| 0029 | 22 | | GA | | 37-0 | SPARE | D40882J | | 29 | | | D41702J | 2 | | | 001-099 | |
| 0029 | 22 | | GA | | 35-0 | 23-34-16 | D03456 | | 29 | | | D41702J | 2 | | | 115-199 | |
| 0030 | 20 | | GA | | 4-0 | SPARE | D40882J | | 31 | | | GD03408 | ST.. | E | | 001-099 | |
| 0030 | 20 | | GA | | 5-0 | 23-34-16 | D03456 | | 31 | | | GD01470 | ST.. | E | | 115-199 | |
| 0031 | 22 | | GA | | 37-0 | SPARE | D40882J | | 30 | | | D41702J | 3 | | | 001-099 | |
| 0031 | 22 | | GA | | 35-0 | 23-34-16 | D03456 | | 30 | | | D41702J | 3 | | | 115-199 | |
| 0032 | 20 | | GA | | 51-0 | 33-21-51 | D41474P | | 4 | | | D40882J | 16 | | | 001-099 | |
| 0032 | 22 | | GA | | 49-0 | 33-21-51 | D41474P | | 4 | | | D03456 | 16 | | | 115-199 | |
| 0033 | 24 | | GK | | 51-0 | 33-21-31 | D41474P | | 7 | | | D40882J | 18 | | | 001-099 | |
| 0033 | 24 | | GK | | 49-0 | 33-21-31 | D41474P | | 7 | | | D03456 | 18 | | | 115-199 | |
| 0034 | 24 | | GK | | 51-0 | 33-21-31 | D41474P | | 9 | | | D40882J | 19 | | | 001-099 | |
| 0034 | 24 | | GK | | 49-0 | 33-21-31 | D41474P | | 9 | | | D03456 | 19 | | | 115-199 | |
| 0035 | 24 | | GK | | 51-0 | 33-21-31 | D41474P | | 10 | | | D40882J | 20 | | | 001-099 | |
| 0035 | 24 | | GK | | 49-0 | 33-21-31 | D41474P | | 10 | | | D03456 | 20 | | | 115-199 | |
| 0036 | 24 | | GK | | 51-0 | 33-21-11 | D41474P | | 14 | | | D40882J | 13 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3576 | 286N3576 | | | P34 TO P21, P22 ATTENDANT PANELS (continued) | | | | | | | | | | | |
| 0036 | 24 | | GK | | 49-0 | 33-21-11 | D41474P | | 14 | | D03456 | | 13 | | 115-199 |
| 0037 | 24 | | GK | | 51-0 | 33-21-11 | D41474P | | 13 | | D40882J | | 14 | | 001-099 |
| 0037 | 24 | | GK | | 49-0 | 33-21-11 | D41474P | | 13 | | D03456 | | 14 | | 115-199 |
| 0038 | 24 | | GK | | 51-0 | 33-21-11 | D41474P | | 12 | | D40882J | | 15 | | 001-099 |
| 0038 | 24 | | GK | | 49-0 | 33-21-11 | D41474P | | 12 | | D03456 | | 15 | | 115-199 |
| 0039 | 20 | | GA | | 51-0 | 33-21-51 | D41474P | | 11 | | D40882J | | 17 | | 001-099 |
| 0039 | 22 | | GA | | 49-0 | 33-21-11 | D41474P | | 11 | | D03456 | | 17 | | 115-199 |
| 0040 | 22 | | GA | | 51-0 | 33-51-11 | D41474P | | 15 | | D40882J | | 38 | | 001-099 |
| 0040 | 22 | | GA | | 49-0 | 33-51-11 | D41474P | | 15 | | D03456 | | 38 | | 115-199 |
| 0041 | 22 | | GA | | 51-0 | 33-51-11 | D41474P | | 16 | | D40882J | | 39 | | 001-099 |
| 0041 | 22 | | GA | | 49-0 | 33-51-11 | D41474P | | 16 | | D03456 | | 39 | | 115-199 |
| 0042 | 22 | | GA | | 51-0 | 33-51-11 | D41474P | | 17 | | D40882J | | 40 | | 001-099 |
| 0042 | 22 | | GA | | 49-0 | 33-51-11 | D41474P | | 17 | | D03456 | | 40 | | 115-199 |
| 0043 | 20 | | GA | | 2-0 | 33-51-11 | D40882J | | 41 | | GD03402 | DC.. | E | | 001-099 |
| 0043 | 20 | | GA | | 5-0 | 33-51-11 | D03456 | | 41 | | GD00509 | DC.. | E | | 115-199 |
| 0044 | 20 | | GA | | 4-0 | 33-21-11 | D40882J | | 34 | | GD03408 | ST.. | E | | 001-099 |
| 0044 | 20 | | GA | | 5-0 | 33-21-11 | D03456 | | 34 | | GD01470 | ST.. | E | | 115-199 |
| 0045 | 20 | | GA | | 51-0 | 24-51-51 | D41474P | | 18 | | D40882J | | 11 | | 001-099 |
| 0045 | 22 | | GA | | 49-0 | 24-51-51 | D41474P | | 18 | | D03456 | | 11 | | 115-199 |
| 0046 | 22 | | GA | | 51-0 | 24-51-51 | D41474P | | 19 | | D40882J | | 9 | | 001-099 |
| 0046 | 22 | | GA | | 49-0 | 24-51-51 | D41474P | | 19 | | D03456 | | 9 | | 115-199 |
| 0047 | 22 | | GA | | 51-0 | 24-51-51 | D41474P | | 20 | | D40882J | | 10 | | 001-099 |
| 0047 | 22 | | GA | | 49-0 | 24-51-51 | D41474P | | 20 | | D03456 | | 10 | | 115-199 |
| 0048 | 22 | | GA | | 131-0 | 33-22-14 | D41474P | | 21 | | D42052J | | 1 | | 001-099 |
| 0048 | 22 | | GA | | 129-0 | 33-22-14 | D41474P | | 21 | | D42052J | | 1 | | 115-199 |
| 0049 | 24 | | GK | | 63-0 | 33-22-11 | D41474P | | 22 | | SP00050 | | 9 | | 001-099 |
| 0049 | 22 | | GA | | 60-0 | 33-22-11 | D41474P | | 22 | | SP00050 | | 9 | | 115-199 |
| 0050 | 22 | | GA | | 26-0 | SPARE | D41474P | | 23 | | D41702J | | 9 | | 115-199 |
| 0051 | 20 | | GA | | 4-0 | 33-22-12 | D07612 | | 3 | | GD01478 | AC.. | E | | 001-099 |
| 0051 | 20 | | GA | | 3-0 | 33-22-12 | D42172J | | 3 | | GD01478 | AC.. | E | | 115-199 |
| 0052 | 22 | | GA | | 6-0 | SPARE | D03456 | | CAP | Y | D03438 | | 11 | | 115-199 |
| 0053 | 20 | | GA | | 2-0 | 24-51-51 | D40882J | | 12 | | GD03400 | DC.. | E | | 001-099 |
| 0054 | 22 | | GA | | 131-0 | 33-22-14 | D42052J | | 4 | | D41474P | | 28 | | 001-099 |
| 0054 | 22 | | GA | | 129-0 | 33-22-14 | D42052J | | 4 | | D41474P | | 27 | | 115-199 |
| 0055 | 20 | | GA | | 6-0 | 33-22-14 | D42052J | | 3 | | GD01834 | AC.. | E | | 001-099 |
| 0055 | 20 | | GA | | 8-0 | 33-22-14 | D42052J | | 3 | | GD01834 | AC.. | E | | 115-199 |
| 0056 | 20 | | GA | | 7-0 | 33-22-14 | L00267 | | =G | C | GD01484 | AC.. | E | | 001-099 |
| 0056 | 20 | | GA | | 3-0 | 33-22-14 | L00267 | | =G | C | GD01484 | AC.. | E | | 115-199 |
| 0057 | 22 | | GA | | 9-0 | 33-22-14 | D42052J | | 2 | | L00267 | =P | C | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3576 | 286N3576 | | | P34 TO P21, P22 ATTENDANT PANELS (continued) | | | | | | | | | | | |
| 0058 | 20 | | GA | | 4-0 | 33-22-14 | L00518 | =G | C | | GD01834 | AC.. | E | | 001-099 |
| 0058 | 20 | | GA | | 5-0 | 33-22-14 | L00518 | =G | C | | GD01834 | AC.. | E | | 115-199 |
| 0059 | 22 | | GA | | 8-0 | 33-27-11 | D03456 | | | 35 | SP01080 | | 9 | | 115-199 |
| 0060 | 22 | | GA | | 8-0 | 33-27-11 | D03456 | | | 37 | SP01074 | | 9 | | 115-199 |
| 0061 | 20 | | GA | | 4-0 | 33-22-14 | L00531 | =G | C | | GD02566 | AC.. | E | | 001-099 |
| 0061 | 22 | | GA | | 8-0 | 33-27-11 | D03456 | | | 36 | SP01078 | | 9 | | 115-199 |
| 0062 | 20 | | GA | | 4-0 | 33-21-31 | D40882J | | | 24 | GD03628 | AC.. | E | | 001-099 |
| 0062 | 20 | | GA | | 38-0 | 33-27-31 | D42052J | | | 5 | SP00532 | | 9 | | 115-199 |
| 0063 | 22 | | GA | | 10-0 | 33-27-31 | D42052J | | | 6 | SP01084 | | 9 | | 115-199 |
| 0064 | 22 | | GA | | 38-0 | 33-27-31 | D42052J | | | 7 | SP00530 | | 9 | | 115-199 |
| 0065 | 22 | | GA | | 10-0 | 33-27-31 | D42052J | | | 8 | SP01086 | | 9 | | 115-199 |
| 0066 | 20 | | GA | | 4-0 | 33-22-14 | D42052J | | | 9 | GD02373 | ST.. | E | | 115-199 |
| 0067 | 22 | | GA | | 10-0 | 33-22-14 | L00531 | =P | C | | L00518 | =P | C | * | 115-199 |
| 0068 | 20 | | GA | | 8-0 | 33-22-14 | L00531 | =G | C | | GD02355 | AC.. | E | | 115-199 |
| 0072 | 24 | | GK | | 131-0 | SPARE | D42052J | | | 11 | D41474P | | 29 | | 001-099 |
| 0076 | 22 | | GA | | 13-0 | 33-22-14 | L00531 | =P | C | | L00518 | =P | C | * | 001-099 |
| 0077 | 22 | | GA | | 51-0 | 33-22-11 | D40882J | | | 2 | D41474P | | 30 | | 001-099 |
| 0077 | 22 | | GA | | 49-0 | 33-22-11 | D41474P | | | 30 | D03456 | | 2 | | 115-199 |
| 0078 | 22 | | GA | | 133-0 | 33-22-14 | D41474P | | | 23 | L00518 | =P | C | * | 001-099 |
| 0078 | 22 | | GA | | 133-0 | 33-22-14 | D41474P | | | 26 | L00518 | =P | C | * | 115-199 |
| 0103 | 22 | | GA | | 29-0 | 33-22-11 | SP01322 | | | 9 | SP01316 | | 9 | | 001-099 |
| 0104 | 22 | | GA | | 22-0 | 33-22-11 | D40882J | | | 6 | SP01314 | | 9 | | 001-099 |
| 0105 | 22 | | GA | | 29-0 | 33-22-11 | SP01320 | | | 9 | SP01314 | | 9 | | 001-099 |
| 0106 | 22 | | GA | | 22-0 | 33-22-11 | D40882J | | | 5 | SP01312 | | 9 | | 001-099 |
| 0107 | 22 | | GA | | 29-0 | 33-22-11 | SP01318 | | | 9 | SP01312 | | 9 | | 001-099 |
| 0122 | 22 | | GA | | 78-0 | 33-27-31 | SP01318 | | | 9 | SP01228 | | 9 | | 001-099 |
| 0123 | 22 | | GA | | 78-0 | 33-27-31 | SP01320 | | | 9 | SP01226 | | 9 | | 001-099 |
| 0124 | 22 | | GA | | 78-0 | 33-27-31 | SP01322 | | | 9 | SP01224 | | 9 | | 001-099 |
| 0129 | 22 | | GA | | 21-0 | 33-22-11 | D03438 | | | 1 | SP01316 | | 9 | | 001-099 |
| 0131 | 20 | | GA | | 2-0 | 23-34-15 | D40882J | | | 25 | GD03402 | DC.. | E | | 001-099 |
| 0131 | 20 | | GA | | 5-0 | 23-34-15 | D03456 | | | 25 | GD00509 | DC.. | E | | 115-199 |
| 0132 | 22 | | GA | | 35-0 | 23-34-16 | D41702J | | | 14 | D03456 | | 21 | | 115-199 |
| 0133 | 22 | | GA | | 35-0 | 23-34-16 | D41702J | | | 15 | D03456 | | 22 | | 115-199 |
| 0134 | 22 | | GA | | 35-0 | 23-34-16 | D41702J | | | 16 | D03456 | | 12 | | 115-199 |
| 0135 | 22 | | GA | | 37-0 | 23-34-15 | D40882J | | | 23 | D41702J | | 8 | | 001-099 |
| 0135 | 22 | | GA | | 35-0 | 23-34-15 | D41702J | | | 8 | D03456 | | 23 | | 115-199 |
| 0136 | 22 | | GA | | 49-0 | 33-22-12 | D41474P | | | 28 | D42172J | | 4 | | 115-199 |
| 0137 | 20 | | GA | | 5-0 | 33-21-31 | D03456 | | | 24 | GD03654 | AC.. | E | | 115-199 |
| 0138 | 22 | | GA | | 35-0 | 23-31-19 | D41820P | | | 12 | D01373 | | 12 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3576 | 286N3576 | | | P34 TO P21, P22 ATTENDANT PANELS (continued) | | | | | | | | | | | |
| 0139 | 22 | | GA | | 35-0 | 23-31-19 | D41820P | | 5 | | D01373 | | 24 | | 001-099 |
| 0140 | 22 | | GA | | 35-0 | 23-31-19 | D41820P | | 4 | | D01373 | | 14 | | 001-099 |
| 0141 | 22 | | GA | | 35-0 | 23-31-19 | D41820P | | 1 | | D01373 | | 1 | | 001-099 |
| 0143 | 22 | | GA | | 35-0 | 23-31-19 | D41820P | | 3 | | D01373 | | 3 | | 001-099 |
| 0144 | 22 | | GA | | 37-0 | 23-31-19 | D01373 | | 20 | | SP00339 | | | 9 | 001-099 |
| 0145 | 20 | | GA | | 4-0 | 23-31-19 | D01373 | | 21 | | GD03704 | AC.. | E | | 001-099 |
| 0146 | 20 | | GA | | 4-0 | 23-31-19 | D01373 | | 5 | | GD01420 | DC.. | E | | 001-099 |
| 0147 | 20 | | GA | | 4-0 | 23-31-19 | D01373 | | 23 | | GD01420 | DC.. | E | | 001-099 |
| 3001B | 22 | | GC | AA | 37-0 | SPARE | D40882J | | 28 | | D41702J | | 6 | | 001-099 |
| 3001B | 22 | | GC | AA | 35-0 | 23-34-16 | D03456 | | 28 | | D41702J | | 6 | | 115-199 |
| 3001R | 22 | | GC | AA | 0-0 | SPARE | D40882J | | 26 | | D41702J | | 5 | | 001-099 |
| 3001R | 22 | | GC | AA | 0-0 | 23-34-16 | D03456 | | 26 | | D41702J | | 5 | | 115-199 |
| 3001Y | 22 | | GC | AA | 0-0 | SPARE | D40882J | | 27 | | D41702J | | 7 | | 001-099 |
| 3001Y | 22 | | GC | AA | 0-0 | 23-34-16 | D03456 | | 27 | | D41702J | | 7 | | 115-199 |
| 3002B | 22 | | GC | AB | 35-0 | 23-31-19 | D41820P | | 2 | | D01373 | | 17 | | 001-099 |
| 3002R | 22 | | GC | AB | 0-0 | 23-31-19 | D41820P | | 6 | | D01373 | | 6 | | 001-099 |
| 3002Y | 22 | | GC | AB | 0-0 | 23-31-19 | D41820P | | 7 | | D01373 | | 18 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3570

Page 10 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3582 | 286N3582 | | | | E3-4 TO LEFT ENTRY DOORS PROXIMITY SWITCHES | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 21-0 | 25-66-11 | D41706P | | 1 | | | SM00001 | | 9 | | 001-099 | |
| 0001 | 20 | | GA | | 22-0 | 25-66-11 | D41706P | | 1 | | | SM00001 | | 9 | | 115-199 | |
| 0002 | 20 | | GA | | 19-0 | 25-66-11 | SM00001 | | | 9 | | L00403 | | C | B | 001-099 | |
| 0002 | 20 | | GA | | 22-0 | 25-66-11 | SM00001 | | | 9 | | L00403 | | C | B | 115-199 | |
| 0003 | 20 | | GA | | 22-0 | 25-66-11 | L00403 | | 2 | B | * | SP00050 | | 9 | | 001-099 | |
| 0003 | 20 | | GA | | 27-0 | 25-66-11 | L00403 | | 2 | B | | SP00050 | | 9 | | 115-199 | |
| 0004 | 20 | | GA | | 20-0 | 25-66-11 | SM00001 | | | 9 | | SM00002 | | 9 | | 001-099 | |
| 0004 | 20 | | GA | | 17-0 | 25-66-11 | SM00001 | | | 9 | | SM00002 | | 9 | | 115-199 | |
| 0005 | 20 | | GA | | 6-0 | 25-66-11 | SM00002 | | | 9 | | L00405 | | C | B | 001-099 | |
| 0005 | 20 | | GA | | 10-0 | 25-66-11 | SM00002 | | | 9 | | L00405 | | C | B | 115-199 | |
| 0006 | 20 | | GA | | 22-0 | 25-66-11 | SP00056 | | | 9 | | L00405 | | 2 | B | * | 001-099 |
| 0006 | 20 | | GA | | 22-0 | 25-66-11 | SP00056 | | | 9 | | L00405 | | 2 | B | | 115-199 |
| 0007 | 20 | | GA | | 85-0 | 25-66-11 | SM00002 | | | 9 | | L00407 | | C | B | 001-099 | |
| 0007 | 20 | | GA | | 90-0 | 25-66-11 | SM00002 | | | 9 | | L00407 | | C | B | 115-199 | |
| 0008 | 20 | | GA | | 27-0 | 25-66-11 | SP00060 | | | 9 | | L00407 | | 2 | B | * | 001-099 |
| 0008 | 20 | | GA | | 33-0 | 25-66-11 | SP00060 | | | 9 | | L00407 | | 2 | B | | 115-199 |
| 0009 | 20 | | GA | | 2-0 | 25-66-11 | L00403 | | 2 | B | * | L00403 | | 1 | B | | 001-099 |
| 0009 | 20 | | GA | | 27-0 | 25-66-11 | SP00050 | | | 9 | | L00403 | | 1 | B | | 115-199 |
| 0010 | 20 | | GA | | 2-0 | 25-66-11 | L00405 | | 2 | B | * | L00405 | | 1 | B | | 001-099 |
| 0010 | 20 | | GA | | 22-0 | 25-66-11 | SP00056 | | | 9 | | L00405 | | 1 | B | | 115-199 |
| 0011 | 20 | | GA | | 2-0 | 25-66-11 | L00407 | | 2 | B | * | L00407 | | 1 | B | | 001-099 |
| 0011 | 20 | | GA | | 33-0 | 25-66-11 | SP00060 | | | 9 | | L00407 | | 1 | B | | 115-199 |
| 0012 | 20 | | GA | | 32-0 | 25-66-11 | SP00052 | | | 9 | | SP01474 | | 9 | | 001-099 | |
| 0012 | 20 | | GA | | 38-0 | 25-66-11 | SP00052 | | | 9 | | SP01474 | | 9 | | 115-199 | |
| 0013 | 20 | | GA | | 30-0 | 25-66-11 | SP00058 | | | 9 | | SP01476 | | 9 | | 001-099 | |
| 0013 | 20 | | GA | | 33-0 | 25-66-11 | SP00058 | | | 9 | | SP01476 | | 9 | | 115-199 | |
| 0014 | 20 | | GA | | 36-0 | 25-66-11 | SP00062 | | | 9 | | SP01466 | | 9 | | 001-099 | |
| 0014 | 20 | | GA | | 43-0 | 25-66-11 | SP00062 | | | 9 | | SP01466 | | 9 | | 115-199 | |
| 0015 | 20 | | GA | | 7-0 | 25-66-11 | GD02916 | | AC.. | E | | SP00732 | | 9 | | 001-099 | |
| 0015 | 20 | | GA | | 12-0 | 25-66-11 | GD00033 | | AC.. | E | | SP00732 | | 9 | | 115-199 | |
| 0016 | 20 | | GA | | 3-0 | 25-66-11 | GD02918 | | AC.. | E | | SP00734 | | 9 | | 001-099 | |
| 0016 | 20 | | GA | | 11-0 | 25-66-11 | GD02918 | | AC.. | E | | SP00734 | | 9 | | 115-199 | |
| 0017 | 20 | | GA | | 8-0 | 25-66-11 | GD02920 | | AC.. | E | | SP00736 | | 9 | | 001-099 | |
| 0017 | 20 | | GA | | 11-0 | 25-66-11 | GD00037 | | AC.. | E | | SP00736 | | 9 | | 115-199 | |
| 2001B | 24 | | GL | AA | 40-0 | 52-71-11 | D41706P | | | 3 | | SP00132 | | 9 | | 001-099 | |
| 2001B | 20 | | GB | AA | 42-0 | 52-71-11 | D41706P | | | 3 | | SP00132 | | 9 | | 115-199 | |
| 2001R | 24 | | GL | AA | 0-0 | 52-71-11 | D41706P | | | 2 | | SP00130 | | 9 | | 001-099 | |
| 2001R | 20 | | GB | AA | 0-0 | 52-71-11 | D41706P | | | 2 | | SP00130 | | 9 | | 115-199 | |
| 2002B | 24 | | GL | AB | 36-0 | 52-71-11 | D41706P | | | 5 | | SP00136 | | 9 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3580

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | To | | | | Effectivity | | | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|---------|-------|-------------|------|---------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Diagram | Equip | | Term | Type | Splice | Equip | Term | Type |
| W3582 | 286N3582 | | | E3-4 TO LEFT ENTRY DOORS PROXIMITY SWITCHES (continued) | | | | | | | | | | | | |
| 2002B | 20 | GB | AB | | 39-0 | 52-71-11 | D41706P | | 5 | | | SP00136 | | 9 | | 115-199 |
| 2002R | 24 | GL | AB | | 0-0 | 52-71-11 | D41706P | | 4 | | | SP00134 | | 9 | | 001-099 |
| 2002R | 20 | GB | AB | | 0-0 | 52-71-11 | D41706P | | 4 | | | SP00134 | | 9 | | 115-199 |
| 2003B | 24 | GL | AC | | 19-0 | 52-71-11 | D41706P | | 7 | | | SP00140 | | 9 | | 001-099 |
| 2003B | 20 | GB | AC | | 17-0 | 52-71-11 | D41706P | | 7 | | | SP00140 | | 9 | | 115-199 |
| 2003R | 24 | GL | AC | | 0-0 | 52-71-11 | D41706P | | 6 | | | SP00138 | | 9 | | 001-099 |
| 2003R | 20 | GB | AC | | 0-0 | 52-71-11 | D41706P | | 6 | | | SP00138 | | 9 | | 115-199 |
| 2004B | 24 | GL | AD | | 50-0 | 52-71-11 | D41706P | | 9 | | | SP00144 | | 9 | | 001-099 |
| 2004B | 20 | GB | AD | | 49-0 | 52-71-11 | D41706P | | 9 | | | SP00144 | | 9 | | 115-199 |
| 2004R | 24 | GL | AD | | 0-0 | 52-71-11 | D41706P | | 8 | | | SP00142 | | 9 | | 001-099 |
| 2004R | 20 | GB | AD | | 0-0 | 52-71-11 | D41706P | | 8 | | | SP00142 | | 9 | | 115-199 |
| 2005B | 24 | GL | AE | | 103-0 | 52-71-11 | D41706P | | 11 | | | SP00148 | | 9 | | 001-099 |
| 2005B | 20 | GB | AE | | 102-0 | 52-71-11 | D41706P | | 11 | | | SP00148 | | 9 | | 115-199 |
| 2005R | 24 | GL | AE | | 0-0 | 52-71-11 | D41706P | | 10 | | | SP00146 | | 9 | | 001-099 |
| 2005R | 20 | GB | AE | | 0-0 | 52-71-11 | D41706P | | 10 | | | SP00146 | | 9 | | 115-199 |
| 2006B | 24 | GL | AF | | 133-0 | 52-71-11 | D41706P | | 13 | | | SP00152 | | 9 | | 001-099 |
| 2006B | 20 | GB | AF | | 133-0 | 52-71-11 | D41706P | | 13 | | | SP00152 | | 9 | | 115-199 |
| 2006R | 24 | GL | AF | | 0-0 | 52-71-11 | D41706P | | 12 | | | SP00150 | | 9 | | 001-099 |
| 2006R | 20 | GB | AF | | 0-0 | 52-71-11 | D41706P | | 12 | | | SP00150 | | 9 | | 115-199 |
| A-GA | | | | | 0-0 | 25-66-11 | S10214 | | BLU | | | SP01474 | | 9 | | ALL |
| A-PA | | | | | 0-0 | 25-66-11 | S10214 | | RED | | | SP00050 | | 9 | | ALL |
| B-GA | | | | | 0-0 | 25-66-11 | S10215 | | BLU | | | SP00732 | | 9 | | ALL |
| B-PA | | | | | 0-0 | 25-66-11 | S10215 | | RED | | | SP00052 | | 9 | | ALL |
| C-GA | | | | | 0-0 | 25-66-11 | S10218 | | BLU | | | SP01476 | | 9 | | ALL |
| C-PA | | | | | 0-0 | 25-66-11 | S10218 | | RED | | | SP00056 | | 9 | | ALL |
| D-GA | | | | | 0-0 | 25-66-11 | S10219 | | BLU | | | SP00734 | | 9 | | ALL |
| D-PA | | | | | 0-0 | 25-66-11 | S10219 | | RED | | | SP00058 | | 9 | | ALL |
| E-GA | | | | | 0-0 | 25-66-11 | S10222 | | BLU | | | SP01466 | | 9 | | ALL |
| E-PA | | | | | 0-0 | 25-66-11 | S10222 | | RED | | | SP00060 | | 9 | | ALL |
| F-GA | | | | | 0-0 | 25-66-11 | S10223 | | BLU | | | SP00736 | | 9 | | ALL |
| F-PA | | | | | 0-0 | 25-66-11 | S10223 | | RED | | | SP00062 | | 9 | | ALL |
| G-GA | | | | | 0-0 | 52-71-11 | S10085 | | BLU | | | SP00132 | | 9 | | ALL |
| G-PA | | | | | 0-0 | 52-71-11 | S10085 | | RED | | | SP00130 | | 9 | | ALL |
| H-GA | | | | | 0-0 | 52-71-11 | S10094 | | BLU | | | SP00136 | | 9 | | ALL |
| H-PA | | | | | 0-0 | 52-71-11 | S10094 | | RED | | | SP00134 | | 9 | | ALL |
| J-GA | | | | | 0-0 | 52-71-11 | S10086 | | BLU | | | SP00140 | | 9 | | ALL |
| J-PA | | | | | 0-0 | 52-71-11 | S10086 | | RED | | | SP00138 | | 9 | | ALL |
| K-GA | | | | | 0-0 | 52-71-11 | S10095 | | BLU | | | SP00144 | | 9 | | ALL |
| K-PA | | | | | 0-0 | 52-71-11 | S10095 | | RED | | | SP00142 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3580

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|--|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3582 | | 286N3582 | | | E3-4 TO LEFT ENTRY DOORS PROXIMITY SWITCHES (continued) | | | | | | | | | | | |
| L-GA | | | | | | 0-0 | 52-71-11 | S10096 | | BLU | | SP00148 | | 9 | | ALL |
| L-PA | | | | | | 0-0 | 52-71-11 | S10096 | | RED | | SP00146 | | 9 | | ALL |
| M-GA | | | | | | 0-0 | 52-71-11 | S10097 | | BLU | | SP00152 | | 9 | | ALL |
| M-PA | | | | | | 0-0 | 52-71-11 | S10097 | | RED | | SP00150 | | 9 | | ALL |

WIRE LIST
D280N032

91-21-11
Section W3580
Page 3 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | Effectivity | | | | |
|------------|-------------|----|----|--|------|----------|---------|-------|------|------|--------|-------------|-------|------|------|---------|
| Wire No. | GA | CO | TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | | Equip | Term | Type | Splice |
| W3592 | 286N3592 | | | ATT NSFSB SIGN- MID-FWD LEFT (STA 735) | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 33-24-12 | D41292P | | 1 | VR | | L00409 | 1 | C | | 001-099 |
| 0002 | 16 | | GA | | 5-0 | 33-24-12 | D41294J | | 1 | VY | | L00409 | 2 | C | | 001-099 |
| 0003 | 20 | | GA | | 5-0 | 33-24-12 | D41296P | | 1 | VG | | L00409 | 3 | C | | 001-099 |
| W3596 | 286N3596 | | | NSFSB-LEFT, MID/FWD (STA 673) | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 5-0 | 33-24-12 | D05028 | | 1 | | | L00536 | 3 | C | | 115-199 |
| 0007 | 20 | | GA | | 5-0 | 33-24-12 | D05028 | | 7 | | | L00536 | 1 | C | | 115-199 |
| 0008 | 16 | | GA | | 5-0 | 33-24-12 | D05028 | | 8 | | | L00536 | 2 | C | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3590

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3614 | 286N3614 | | | | FLUORESCENT LIGHTING-CEILING,RIGHT FORWARD | | | | | | | | | | | |
| 0010 | 20 | | GA | | 9-0 | 33-21-51 | D00642 | | | 10 | | SM00010 | | 9 | | ALL |
| 0011 | 20 | | GA | | 9-0 | 33-21-21 | D00642 | | | 1 | | SM00011 | | 9 | | ALL |
| 0012 | 20 | | GA | | 3-0 | 33-21-21 | D00642 | | | 2 | | GD00645 | AC.. | E | | 001-099 |
| 0012 | 20 | | GA | | 3-0 | 33-21-21 | D00642 | | | 2 | | GD00645 | AC.R | E | | 115-199 |
| 0013 | 24 | | GK | | 9-0 | 33-21-21 | D00642 | | | 3 | | SM00013 | | 9 | | ALL |
| 0014 | 20 | | GA | | 3-0 | 33-21-21 | D00642 | | | 4 | | GD00646 | ST.. | E | | 001-099 |
| 0014 | 20 | | GA | | 3-0 | 33-21-21 | D00642 | | | 4 | | GD00646 | ST.R | E | | 115-199 |
| 0015 | 22 | | GA | | 13-0 | 33-21-21 | D00642 | | | 5 | | D00644 | | 5 | | ALL |
| 0016 | 22 | | GA | | 13-0 | 33-21-21 | D00642 | | | 6 | | D00644 | | 6 | | ALL |
| 0017 | 22 | | GA | | 13-0 | 33-21-21 | D00642 | | | 7 | | D00644 | | 7 | | ALL |
| 0018 | 22 | | GA | | 13-0 | 33-21-21 | D00642 | | | 8 | | D00644 | | 8 | | ALL |
| 0019 | 22 | | GA | | 13-0 | 33-21-21 | D00642 | | | 9 | | D00644 | | 9 | | ALL |
| 0021 | 20 | | GA | | 5-0 | 33-21-21 | D00646 | | | 1 | | SM00021 | | 9 | | 001-099 |
| 0021 | 20 | | GA | | 7-0 | 33-21-21 | D00650 | | | 1 | | SM00041 | | 9 | | 115-199 |
| 0022 | 20 | | GA | | 3-0 | 33-21-21 | D00646 | | | 2 | | GD00647 | AC.. | E | | 001-099 |
| 0022 | 20 | | GA | | 8-0 | 33-21-21 | D00650 | | | 2 | | GD00651 | AC.R | E | | 115-199 |
| 0023 | 24 | | GK | | 5-0 | 33-21-21 | D00646 | | | 3 | | SM00023 | | 9 | | 001-099 |
| 0023 | 24 | | GK | | 7-0 | 33-21-21 | D00650 | | | 3 | | SM00043 | | 9 | | 115-199 |
| 0024 | 20 | | GA | | 3-0 | 33-21-21 | D00646 | | | 4 | | GD00648 | ST.. | E | | 001-099 |
| 0024 | 20 | | GA | | 7-0 | 33-21-21 | D00650 | | | 4 | | GD00652 | ST.R | E | | 115-199 |
| 0025 | 22 | | GA | | 13-0 | 33-21-21 | D00646 | | | 5 | | D04464 | | 5 | | 001-099 |
| 0025 | 22 | | GA | | 12-0 | 33-21-21 | D00650 | | | 5 | | D00652 | | 5 | | 115-199 |
| 0026 | 22 | | GA | | 13-0 | 33-21-21 | D00646 | | | 6 | | D04464 | | 6 | | 001-099 |
| 0026 | 22 | | GA | | 12-0 | 33-21-21 | D00650 | | | 6 | | D00652 | | 6 | | 115-199 |
| 0027 | 22 | | GA | | 13-0 | 33-21-21 | D00646 | | | 7 | | D04464 | | 7 | | 001-099 |
| 0027 | 22 | | GA | | 12-0 | 33-21-21 | D00650 | | | 7 | | D00652 | | 7 | | 115-199 |
| 0028 | 22 | | GA | | 13-0 | 33-21-21 | D00646 | | | 8 | | D04464 | | 8 | | 001-099 |
| 0028 | 22 | | GA | | 12-0 | 33-21-21 | D00650 | | | 8 | | D00652 | | 8 | | 115-199 |
| 0029 | 22 | | GA | | 13-0 | 33-21-21 | D00646 | | | 9 | | D04464 | | 9 | | 001-099 |
| 0029 | 22 | | GA | | 12-0 | 33-21-21 | D00650 | | | 9 | | D00652 | | 9 | | 115-199 |
| 0031 | 20 | | GA | | 7-0 | 33-21-21 | D00648 | | | 1 | | SM00031 | | 9 | | 115-199 |
| 0032 | 20 | | GA | | 3-0 | 33-21-21 | D00648 | | | 2 | | GD00649 | AC.R | E | | 115-199 |
| 0033 | 24 | | GK | | 7-0 | 33-21-21 | D00648 | | | 3 | | SM00033 | | 9 | | 115-199 |
| 0034 | 20 | | GA | | 3-0 | 33-21-21 | D00648 | | | 4 | | GD00650 | ST.R | E | | 115-199 |
| 0040 | 20 | | GA | | 5-0 | 33-21-51 | D00656 | | | 10 | | SM00040 | | 9 | | 001-099 |
| 0041 | 20 | | GA | | 5-0 | 33-21-21 | D00650 | | | 1 | | SM00041 | | 9 | | 001-099 |
| 0042 | 20 | | GA | | 9-0 | 33-21-21 | D00650 | | | 2 | | GD00651 | AC.. | E | | 001-099 |
| 0043 | 24 | | GK | | 5-0 | 33-21-21 | D00650 | | | 3 | | SM00043 | | 9 | | 001-099 |
| 0044 | 20 | | GA | | 8-0 | 33-21-21 | D00650 | | | 4 | | GD00652 | ST.. | E | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3610

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3614 | 286N3614 | | | FLUORESCENT LIGHTING-CEILING,RIGHT FORWARD (continued) | | | | | | | | | | | |
| 0045 | 22 | | GA | | 13-0 | 33-21-21 | D00650 | | | | D00652 | | 5 | | 001-099 |
| 0046 | 22 | | GA | | 13-0 | 33-21-21 | D00650 | | | | D00652 | | 6 | | 001-099 |
| 0047 | 22 | | GA | | 13-0 | 33-21-21 | D00650 | | | | D00652 | | 7 | | 001-099 |
| 0048 | 22 | | GA | | 13-0 | 33-21-21 | D00650 | | | | D00652 | | 8 | | 001-099 |
| 0049 | 22 | | GA | | 13-0 | 33-21-21 | D00650 | | | | D00652 | | 9 | | 001-099 |
| 0051 | 20 | | GA | | 5-0 | 33-21-21 | D00656 | | | | SM00051 | | | 9 | 001-099 |
| 0051 | 20 | | GA | | 4-0 | 33-21-21 | D00640 | | | | SM00001 | | | 9 | 115-199 |
| 0052 | 20 | | GA | | 3-0 | 33-21-21 | D00656 | | | | GD00655 | AC.. | E | | 001-099 |
| 0052 | 20 | | GA | | 3-0 | 33-21-21 | D00640 | | | | GD02043 | AC.R | E | | 115-199 |
| 0053 | 24 | | GK | | 5-0 | 33-21-21 | D00656 | | | | SM00053 | | | 9 | 001-099 |
| 0053 | 24 | | GK | | 4-0 | 33-21-21 | D00640 | | | | SM00003 | | | 9 | 115-199 |
| 0054 | 20 | | GA | | 3-0 | 33-21-21 | D00656 | | | | GD00656 | ST.. | E | | 001-099 |
| 0054 | 20 | | GA | | 3-0 | 33-21-21 | D00640 | | | | GD02044 | ST.R | E | | 115-199 |
| 0055 | 22 | | GA | | 14-0 | 33-21-21 | D00656 | | | | D00658 | | 5 | | 001-099 |
| 0056 | 22 | | GA | | 14-0 | 33-21-21 | D00656 | | | | D00658 | | 6 | | 001-099 |
| 0057 | 22 | | GA | | 14-0 | 33-21-21 | D00656 | | | | D00658 | | 7 | | 001-099 |
| 0058 | 22 | | GA | | 14-0 | 33-21-21 | D00656 | | | | D00658 | | 8 | | 001-099 |
| 0059 | 22 | | GA | | 14-0 | 33-21-21 | D00656 | | | | D00658 | | 9 | | 001-099 |
| 0061 | 20 | | GA | | 4-0 | 33-21-21 | D04462 | | | | SM00001 | | | 9 | 115-199 |
| 0062 | 20 | | GA | | 6-0 | 33-21-21 | D04462 | | | | GD01767 | AC.R | E | | 115-199 |
| 0063 | 24 | | GK | | 4-0 | 33-21-21 | D04462 | | | | SM00003 | | | 9 | 115-199 |
| 0064 | 20 | | GA | | 6-0 | 33-21-21 | D04462 | | | | GD01768 | ST.R | E | | 115-199 |
| 0070 | 20 | | GA | | 7-0 | 33-21-51 | D00656 | | 10 | | SM00070 | | | 9 | 115-199 |
| 0071 | 20 | | GA | | 7-0 | 33-21-22 | D00656 | | | | SM00071 | | | 9 | 115-199 |
| 0072 | 20 | | GA | | 2-0 | 33-21-22 | D00656 | | | | GD00655 | AC.R | E | | 115-199 |
| 0073 | 24 | | GK | | 7-0 | 33-21-22 | D00656 | | | | SM00073 | | | 9 | 115-199 |
| 0074 | 20 | | GA | | 2-0 | 33-21-22 | D00656 | | | | GD00656 | ST.R | E | | 115-199 |
| 0075 | 22 | | GA | | 13-0 | 33-21-22 | D00656 | | | | D00658 | | 5 | | 115-199 |
| 0076 | 22 | | GA | | 13-0 | 33-21-22 | D00656 | | | | D00658 | | 6 | | 115-199 |
| 0077 | 22 | | GA | | 13-0 | 33-21-22 | D00656 | | | | D00658 | | 7 | | 115-199 |
| 0078 | 22 | | GA | | 13-0 | 33-21-22 | D00656 | | | | D00658 | | 8 | | 115-199 |
| 0079 | 22 | | GA | | 13-0 | 33-21-22 | D00656 | | | | D00658 | | 9 | | 115-199 |
| 0081 | 20 | | GA | | 11-0 | 33-21-21 | D04462 | | | | SM00081 | | | 9 | 001-099 |
| 0082 | 20 | | GA | | 7-0 | 33-21-21 | D04462 | | | | GD01767 | AC.. | E | | 001-099 |
| 0083 | 24 | | GK | | 11-0 | 33-21-21 | D04462 | | | | SM00083 | | | 9 | 001-099 |
| 0084 | 20 | | GA | | 7-0 | 33-21-21 | D04462 | | | | GD01768 | ST.. | E | | 001-099 |
| 0091 | 20 | | GA | | 14-0 | 33-21-21 | D04590 | | | | SM00091 | | | 9 | 115-199 |
| 0092 | 20 | | GA | | 3-0 | 33-21-21 | D04590 | | | | GD02155 | AC.R | E | | 115-199 |
| 0093 | 24 | | GK | | 14-0 | 33-21-21 | D04590 | | | | SM00093 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3610

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3614 | 286N3614 | | | | FLUORESCENT LIGHTING-CEILING,RIGHT FORWARD (continued) | | | | | | | | | | | | |
| 0094 | 20 | | GA | | 3-0 | 33-21-21 | | D04590 | | | 4 | | GD02156 | ST.R | E | | 115-199 |
| 0121 | 20 | | GA | | 7-0 | 33-21-21 | | D00646 | | | 1 | | SM00121 | | 9 | | 115-199 |
| 0122 | 20 | | GA | | 3-0 | 33-21-21 | | D00646 | | | 2 | | GD00647 | AC.R | E | | 115-199 |
| 0123 | 24 | | GK | | 7-0 | 33-21-21 | | D00646 | | | 3 | | SM00123 | | 9 | | 115-199 |
| 0124 | 20 | | GA | | 3-0 | 33-21-21 | | D00646 | | | 4 | | GD00648 | ST.R | E | | 115-199 |
| 0125 | 22 | | GA | | 14-0 | 33-21-21 | | D00646 | | | 5 | | D04464 | | 5 | | 115-199 |
| 0126 | 22 | | GA | | 14-0 | 33-21-21 | | D00646 | | | 6 | | D04464 | | 6 | | 115-199 |
| 0127 | 22 | | GA | | 14-0 | 33-21-21 | | D00646 | | | 7 | | D04464 | | 7 | | 115-199 |
| 0128 | 22 | | GA | | 14-0 | 33-21-21 | | D00646 | | | 8 | | D04464 | | 8 | | 115-199 |
| 0129 | 22 | | GA | | 14-0 | 33-21-21 | | D00646 | | | 9 | | D04464 | | 9 | | 115-199 |
| 0301 | 20 | | GA | | 39-0 | 33-21-21 | | D40476P | | | 1 | | SM00081 | | 9 | | 001-099 |
| 0301 | 20 | | GA | | 45-0 | 33-21-21 | | D40476P | | | 1 | | SM00001 | | 9 | | 115-199 |
| 0303 | 24 | | GK | | 39-0 | 33-21-21 | | D40476P | | | 3 | | SM00083 | | 9 | | 001-099 |
| 0303 | 24 | | GK | | 45-0 | 33-21-21 | | D40476P | | | 3 | | SM00003 | | 9 | | 115-199 |
| 0308 | 20 | | GA | | 73-0 | SPARE | | D40476P | | | 8 | | D41814J | | 8 | | 001-099 |
| 0309 | 20 | | GA | | 73-0 | SPARE | | D40476P | | | 9 | | D41814J | | 9 | | 001-099 |
| 0310 | 20 | | GA | | 37-0 | 33-21-51 | | D40476P | | | 10 | | SM00010 | | 9 | | 001-099 |
| 0310 | 20 | | GA | | 37-0 | 33-21-51 | | D40476P | | | 4 | | SM00010 | | 9 | | 115-199 |
| 0311 | 20 | | GA | | 4-0 | 33-21-21 | | SM00081 | | | 9 | | SM00011 | | 9 | | 001-099 |
| 0311 | 20 | | GA | | 11-0 | 33-21-21 | | SM00001 | | | 9 | | SM00011 | | 9 | | 115-199 |
| 0312 | 20 | | GA | | 73-0 | SPARE | | D40476P | | | 12 | | D41814J | | 12 | | 001-099 |
| 0313 | 24 | | GK | | 4-0 | 33-21-21 | | SM00083 | | | 9 | | SM00013 | | 9 | | 001-099 |
| 0313 | 24 | | GK | | 11-0 | 33-21-21 | | SM00003 | | | 9 | | SM00013 | | 9 | | 115-199 |
| 0320 | 20 | | GA | | 28-0 | 33-21-51 | | SM00010 | | | 9 | | SM00040 | | 9 | | 001-099 |
| 0320 | 20 | | GA | | 25-0 | 33-21-51 | | SM00010 | | | 9 | | SM00070 | | 9 | | 115-199 |
| 0321 | 20 | | GA | | 8-0 | 33-21-21 | | SM00011 | | | 9 | | SM00021 | | 9 | | 001-099 |
| 0323 | 24 | | GK | | 8-0 | 33-21-21 | | SM00013 | | | 9 | | SM00023 | | 9 | | 001-099 |
| 0331 | 20 | | GA | | 12-0 | 33-21-21 | | SM00021 | | | 9 | | SM00041 | | 9 | | 001-099 |
| 0333 | 24 | | GK | | 12-0 | 33-21-21 | | SM00023 | | | 9 | | SM00043 | | 9 | | 001-099 |
| 0340 | 20 | | GA | | 11-0 | 33-21-51 | | D41814J | | | 10 | | SM00040 | | 9 | | 001-099 |
| 0341 | 20 | | GA | | 12-0 | 33-21-21 | | SM00041 | | | 9 | | SM00051 | | 9 | | 001-099 |
| 0343 | 24 | | GK | | 12-0 | 33-21-21 | | SM00043 | | | 9 | | SM00053 | | 9 | | 001-099 |
| 0351 | 20 | | GA | | 11-0 | 33-21-21 | | SM00051 | | | 9 | | D41814J | | 7 | | 001-099 |
| 0353 | 24 | | GK | | 11-0 | 33-21-21 | | SM00053 | | | 9 | | D41814J | | 6 | | 001-099 |
| 0370 | 20 | | GA | | 13-0 | 33-21-51 | | SM00070 | | | 9 | | D41814J | | 4 | | 115-199 |
| 0371 | 20 | | GA | | 13-0 | 33-21-22 | | SM00071 | | | 9 | | D41814J | | 1 | | 115-199 |
| 0373 | 24 | | GK | | 13-0 | 33-21-22 | | SM00073 | | | 9 | | D41814J | | 3 | | 115-199 |
| 0411 | 20 | | GA | | 5-0 | 33-21-21 | | SM00011 | | | 9 | | SM00121 | | 9 | | 115-199 |
| 0413 | 24 | | GK | | 5-0 | 33-21-21 | | SM00013 | | | 9 | | SM00123 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3610

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|-------|----------|---------|------|--------|-------|------|---------|--------|-------------|---|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3614 | 286N3614 | | | | FLUORESCENT LIGHTING-CEILING,RIGHT FORWARD (continued) | | | | | | | | | | | | |
| 0421 | 20 | | GA | | 5-0 | | 33-21-21 | SM00121 | | | 9 | | SM00031 | | | 9 | 115-199 |
| 0423 | 24 | | GK | | 5-0 | | 33-21-21 | SM00123 | | | 9 | | SM00033 | | | 9 | 115-199 |
| 0431 | 20 | | GA | | 8-0 | | 33-21-21 | SM00031 | | | 9 | | SM00041 | | | 9 | 115-199 |
| 0433 | 24 | | GK | | 8-0 | | 33-21-21 | SM00033 | | | 9 | | SM00043 | | | 9 | 115-199 |
| 0441 | 20 | | GA | | 12-0 | | 33-21-22 | SM00091 | | | 9 | | SM00071 | | | 9 | 115-199 |
| 0443 | 24 | | GK | | 12-0 | | 33-21-22 | SM00093 | | | 9 | | SM00073 | | | 9 | 115-199 |
| 0491 | 20 | | GA | | 1-0 | | 33-21-21 | SM00041 | | | 9 | | SM00091 | | | 9 | 115-199 |
| 0493 | 24 | | GK | | 1-0 | | 33-21-21 | SM00043 | | | 9 | | SM00093 | | | 9 | 115-199 |
| W3616 | 286N3616 | | | | FLUORESCENT LIGHTING-CEILING,RIGHT MID | | | | | | | | | | | | |
| 0001 | 20 | | GA | | 6-2 | | 33-21-22 | D00660 | | | 1 | | SM00001 | | | 9 | 001-099 |
| 0002 | 20 | | GA | | 2-9 | | 33-21-22 | D00660 | | | 2 | | GD00657 | AC.. | | E | 001-099 |
| 0003 | 24 | | GK | | 6-2 | | 33-21-22 | D00660 | | | 3 | | SM00003 | | | 9 | 001-099 |
| 0004 | 20 | | GA | | 2-10 | | 33-21-22 | D00660 | | | 4 | | GD00658 | ST.. | | E | 001-099 |
| 0005 | 22 | | GA | | 12-7 | | 33-21-22 | D00660 | | | 5 | | D00662 | | | 5 | 001-099 |
| 0006 | 22 | | GA | | 12-7 | | 33-21-22 | D00660 | | | 6 | | D00662 | | | 6 | 001-099 |
| 0007 | 22 | | GA | | 12-7 | | 33-21-22 | D00660 | | | 7 | | D00662 | | | 7 | 001-099 |
| 0008 | 22 | | GA | | 12-7 | | 33-21-22 | D00660 | | | 8 | | D00662 | | | 8 | 001-099 |
| 0009 | 22 | | GA | | 12-7 | | 33-21-22 | D00660 | | | 9 | | D00662 | | | 9 | 001-099 |
| 0011 | 20 | | GA | | 13-3 | | 33-21-22 | D00664 | | | 1 | | SM00001 | | | 9 | 001-099 |
| 0012 | 20 | | GA | | 2-8 | | 33-21-22 | D00664 | | | 2 | | GD00659 | AC.. | | E | 001-099 |
| 0013 | 24 | | GK | | 6-10 | | 33-21-22 | D00664 | | | 3 | | SM00013 | | | 9 | 001-099 |
| 0014 | 20 | | GA | | 2-8 | | 33-21-22 | D00664 | | | 4 | | GD00660 | ST.. | | E | 001-099 |
| 0015 | 22 | | GA | | 12-7 | | 33-21-22 | D00664 | | | 5 | | D00666 | | | 5 | 001-099 |
| 0016 | 22 | | GA | | 12-7 | | 33-21-22 | D00664 | | | 6 | | D00666 | | | 6 | 001-099 |
| 0017 | 22 | | GA | | 12-7 | | 33-21-22 | D00664 | | | 7 | | D00666 | | | 7 | 001-099 |
| 0018 | 22 | | GA | | 12-7 | | 33-21-22 | D00664 | | | 8 | | D00666 | | | 8 | 001-099 |
| 0019 | 22 | | GA | | 12-7 | | 33-21-22 | D00664 | | | 9 | | D00666 | | | 9 | 001-099 |
| 0020 | 20 | | GA | | 6-8 | | 33-21-51 | D00668 | | | 10 | | SM00020 | | | 9 | 001-099 |
| 0021 | 20 | | GA | | 6-8 | | 33-21-22 | D00668 | | | 1 | | SM00021 | | | 9 | 001-099 |
| 0022 | 20 | | GA | | 2-8 | | 33-21-22 | D00668 | | | 2 | | GD00661 | AC.. | | E | 001-099 |
| 0023 | 24 | | GK | | 6-8 | | 33-21-22 | D00668 | | | 3 | | SM00023 | | | 9 | 001-099 |
| 0024 | 20 | | GA | | 2-9 | | 33-21-22 | D00668 | | | 4 | | GD00662 | ST.. | | E | 001-099 |
| 0025 | 22 | | GA | | 11-11 | | 33-21-22 | D00668 | | | 5 | | D00670 | | | 5 | 001-099 |
| 0026 | 22 | | GA | | 11-11 | | 33-21-22 | D00668 | | | 6 | | D00670 | | | 6 | 001-099 |
| 0027 | 22 | | GA | | 11-11 | | 33-21-22 | D00668 | | | 7 | | D00670 | | | 7 | 001-099 |
| 0028 | 22 | | GA | | 11-11 | | 33-21-22 | D00668 | | | 8 | | D00670 | | | 8 | 001-099 |
| 0029 | 22 | | GA | | 11-11 | | 33-21-22 | D00668 | | | 9 | | D00670 | | | 9 | 001-099 |
| 0081 | 20 | | GA | | 8-0 | | 33-21-22 | D00660 | | | 1 | | SM00081 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3610

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3616 | 286N3616 | | | | FLUORESCENT LIGHTING-CEILING,RIGHT MID (continued) | | | | | | | | | | | |
| 0082 | 20 | | GA | | 3-0 | 33-21-22 | D00660 | | 2 | | GD00657 | AC.R | E | | 115-199 | |
| 0083 | 24 | | GK | | 8-0 | 33-21-22 | D00660 | | 3 | | SM00083 | | 9 | | 115-199 | |
| 0084 | 20 | | GA | | 3-0 | 33-21-22 | D00660 | | 4 | | GD00658 | ST.R | E | | 115-199 | |
| 0085 | 22 | | GA | | 12-0 | 33-21-22 | D00660 | | 5 | | D00662 | | 5 | | 115-199 | |
| 0086 | 22 | | GA | | 12-0 | 33-21-22 | D00660 | | 6 | | D00662 | | 6 | | 115-199 | |
| 0087 | 22 | | GA | | 12-0 | 33-21-22 | D00660 | | 7 | | D00662 | | 7 | | 115-199 | |
| 0088 | 22 | | GA | | 12-0 | 33-21-22 | D00660 | | 8 | | D00662 | | 8 | | 115-199 | |
| 0089 | 22 | | GA | | 12-0 | 33-21-22 | D00660 | | 9 | | D00662 | | 9 | | 115-199 | |
| 0091 | 20 | | GA | | 7-0 | 33-21-22 | D00664 | | 1 | | SM00091 | | 9 | | 115-199 | |
| 0092 | 20 | | GA | | 5-0 | 33-21-22 | D00664 | | 2 | | GD00659 | AC.R | E | | 115-199 | |
| 0093 | 24 | | GK | | 7-0 | 33-21-22 | D00664 | | 3 | | SM00093 | | 9 | | 115-199 | |
| 0094 | 20 | | GA | | 5-0 | 33-21-22 | D00664 | | 4 | | GD00660 | ST.R | E | | 115-199 | |
| 0095 | 22 | | GA | | 14-0 | 33-21-22 | D00664 | | 5 | | D00666 | | 5 | | 115-199 | |
| 0096 | 22 | | GA | | 14-0 | 33-21-22 | D00664 | | 6 | | D00666 | | 6 | | 115-199 | |
| 0097 | 22 | | GA | | 14-0 | 33-21-22 | D00664 | | 7 | | D00666 | | 7 | | 115-199 | |
| 0098 | 22 | | GA | | 14-0 | 33-21-22 | D00664 | | 8 | | D00666 | | 8 | | 115-199 | |
| 0099 | 22 | | GA | | 14-0 | 33-21-22 | D00664 | | 9 | | D00666 | | 9 | | 115-199 | |
| 0101 | 20 | | GA | | 9-0 | 33-21-22 | D00668 | | 1 | | SM00101 | | 9 | | 115-199 | |
| 0102 | 20 | | GA | | 4-0 | 33-21-22 | D00668 | | 2 | | GD00661 | AC.R | E | | 115-199 | |
| 0103 | 24 | | GK | | 9-0 | 33-21-22 | D00668 | | 3 | | SM00103 | | 9 | | 115-199 | |
| 0104 | 20 | | GA | | 4-0 | 33-21-22 | D00668 | | 4 | | GD00662 | ST.R | E | | 115-199 | |
| 0105 | 22 | | GA | | 13-0 | 33-21-22 | D00668 | | 5 | | D00670 | | 5 | | 115-199 | |
| 0106 | 22 | | GA | | 13-0 | 33-21-22 | D00668 | | 6 | | D00670 | | 6 | | 115-199 | |
| 0107 | 22 | | GA | | 13-0 | 33-21-22 | D00668 | | 7 | | D00670 | | 7 | | 115-199 | |
| 0108 | 22 | | GA | | 13-0 | 33-21-22 | D00668 | | 8 | | D00670 | | 8 | | 115-199 | |
| 0109 | 22 | | GA | | 13-0 | 33-21-22 | D00668 | | 9 | | D00670 | | 9 | | 115-199 | |
| 0110 | 20 | | GA | | 9-0 | 33-21-51 | D00668 | | 10 | | SM00110 | | 9 | | 115-199 | |
| 0303 | 24 | | GK | | 8-5 | 33-21-22 | SM00003 | | 9 | | SM00013 | | 9 | | 001-099 | |
| 0306 | 24 | | GK | | 6-3 | 33-21-22 | D41814P | | 6 | | SM00003 | | 9 | | 001-099 | |
| 0307 | 20 | | GA | | 6-3 | 33-21-22 | D41814P | | 7 | | SM00001 | | 9 | | 001-099 | |
| 0308 | 20 | | GA | | 31-7 | SPARE | D41814P | | 8 | | D41816J | | 8 | | 001-099 | |
| 0309 | 20 | | GA | | 18-7 | 33-21-22 | SM00001 | | 9 | | SM00021 | | 9 | | 001-099 | |
| 0310 | 20 | | GA | | 22-10 | 33-21-51 | D41814P | | 10 | | SM00020 | | 9 | | 001-099 | |
| 0310 | 20 | | GA | | 23-0 | 33-21-51 | D41814P | | 4 | | SM00110 | | 9 | | 115-199 | |
| 0312 | 20 | | GA | | 31-7 | SPARE | D41814P | | 12 | | D41816J | | 12 | | 001-099 | |
| 0313 | 24 | | GK | | 12-2 | 33-21-22 | SM00013 | | 9 | | SM00023 | | 9 | | 001-099 | |
| 0320 | 20 | | GA | | 10-10 | 33-21-51 | SM00020 | | 9 | | D41816J | | 10 | | 001-099 | |
| 0320 | 20 | | GA | | 7-0 | 33-21-51 | SM00110 | | 9 | | D41816J | | 4 | | 115-199 | |
| 0321 | 20 | | GA | | 10-10 | 33-21-22 | SM00021 | | 9 | | D41816J | | 9 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3610

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|----|---|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3616 | 286N3616 | | | FLUORESCENT LIGHTING-CEILING,RIGHT MID (continued) | | | | | | | | | | | |
| 0323 | 24 | | GK | 10-10 | 33-21-22 | SM00023 | | | 9 | | D41816J | | 6 | | 001-099 |
| 0371 | 20 | | GA | 7-0 | 33-21-22 | D41814P | | | 1 | | SM00081 | | 9 | | 115-199 |
| 0373 | 24 | | GK | 7-0 | 33-21-22 | D41814P | | | 3 | | SM00083 | | 9 | | 115-199 |
| 0381 | 20 | | GA | 8-0 | 33-21-22 | SM00081 | | | 9 | | SM00091 | | 9 | | 115-199 |
| 0383 | 24 | | GK | 8-0 | 33-21-22 | SM00083 | | | 9 | | SM00093 | | 9 | | 115-199 |
| 0391 | 20 | | GA | 12-0 | 33-21-22 | SM00091 | | | 9 | | SM00101 | | 9 | | 115-199 |
| 0393 | 24 | | GK | 12-0 | 33-21-22 | SM00093 | | | 9 | | SM00103 | | 9 | | 115-199 |
| 0401 | 20 | | GA | 7-0 | 33-21-22 | SM00101 | | | 9 | | D41816J | | 1 | | 115-199 |
| 0403 | 24 | | GK | 7-0 | 33-21-22 | SM00103 | | | 9 | | D41816J | | 3 | | 115-199 |
| W3618 | 286N3618 | | | FLUORESCENT LIGHTING-CEILING,RIGHT AFT | | | | | | | | | | | |
| 0011 | 20 | | GA | 10-0 | 33-21-23 | D00674 | | | 1 | | SM00011 | | 9 | | 001-099 |
| 0012 | 20 | | GA | 4-0 | 33-21-23 | D00674 | | | 2 | | GD00663 | AC.. | E | | 001-099 |
| 0013 | 24 | | GK | 10-0 | 33-21-23 | D00674 | | | 3 | | SM00013 | | 9 | | 001-099 |
| 0014 | 20 | | GA | 4-0 | 33-21-23 | D00674 | | | 4 | | GD00664 | ST.. | E | | 001-099 |
| 0015 | 22 | | GA | 13-0 | 33-21-23 | D00674 | | | 5 | | D00676 | | 5 | | 001-099 |
| 0016 | 22 | | GA | 13-0 | 33-21-23 | D00674 | | | 6 | | D00676 | | 6 | | 001-099 |
| 0017 | 22 | | GA | 13-0 | 33-21-23 | D00674 | | | 7 | | D00676 | | 7 | | 001-099 |
| 0018 | 22 | | GA | 13-0 | 33-21-23 | D00674 | | | 8 | | D00676 | | 8 | | 001-099 |
| 0019 | 22 | | GA | 13-0 | 33-21-23 | D00674 | | | 9 | | D00676 | | 9 | | 001-099 |
| 0020 | 20 | | GA | 24-0 | 33-21-51 | D00678 | | | 10 | | D41816P | | 10 | | 001-099 |
| 0021 | 20 | | GA | 11-0 | 33-21-23 | D00678 | | | 1 | | SM00021 | | 9 | | 001-099 |
| 0022 | 20 | | GA | 5-0 | 33-21-23 | D00678 | | | 2 | | GD00665 | AC.. | E | | 001-099 |
| 0023 | 24 | | GK | 11-0 | 33-21-23 | D00678 | | | 3 | | SM00023 | | 9 | | 001-099 |
| 0024 | 20 | | GA | 5-0 | 33-21-23 | D00678 | | | 4 | | GD00666 | ST.. | E | | 001-099 |
| 0025 | 22 | | GA | 15-0 | 33-21-23 | D00678 | | | 5 | | D00680 | | 5 | | 001-099 |
| 0026 | 22 | | GA | 15-0 | 33-21-23 | D00678 | | | 6 | | D00680 | | 6 | | 001-099 |
| 0027 | 22 | | GA | 15-0 | 33-21-23 | D00678 | | | 7 | | D00680 | | 7 | | 001-099 |
| 0028 | 22 | | GA | 15-0 | 33-21-23 | D00678 | | | 8 | | D00680 | | 8 | | 001-099 |
| 0029 | 22 | | GA | 15-0 | 33-21-23 | D00678 | | | 9 | | D00680 | | 9 | | 001-099 |
| 0031 | 20 | | GA | 19-0 | 33-21-23 | D00682 | | | 1 | | SM00021 | | 9 | | 001-099 |
| 0032 | 20 | | GA | 3-0 | 33-21-23 | D00682 | | | 2 | | GD02913 | AC.. | E | | 001-099 |
| 0033 | 24 | | GK | 19-0 | 33-21-23 | D00682 | | | 3 | | SM00023 | | 9 | | 001-099 |
| 0034 | 20 | | GA | 3-0 | 33-21-23 | D00682 | | | 4 | | GD02917 | ST.. | E | | 001-099 |
| 0121 | 20 | | GA | 7-0 | 33-21-23 | D00674 | | | 1 | | SM00121 | | 9 | | 115-199 |
| 0122 | 20 | | GA | 3-0 | 33-21-23 | D00674 | | | 2 | | GD00663 | AC.R | E | | 115-199 |
| 0123 | 24 | | GK | 7-0 | 33-21-23 | D00674 | | | 3 | | SM00123 | | 9 | | 115-199 |
| 0124 | 20 | | GA | 3-0 | 33-21-23 | D00674 | | | 4 | | GD00664 | ST.R | E | | 115-199 |
| 0125 | 22 | | GA | 13-0 | 33-21-23 | D00674 | | | 5 | | D00676 | | 5 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3610

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3618 | 286N3618 | | | FLUORESCENT LIGHTING-CEILING,RIGHT AFT (continued) | | | | | | | | | | | |
| 0126 | 22 | | GA | | 13-0 | 33-21-23 | D00674 | | 6 | | D00676 | | 6 | | 115-199 |
| 0127 | 22 | | GA | | 13-0 | 33-21-23 | D00674 | | 7 | | D00676 | | 7 | | 115-199 |
| 0128 | 22 | | GA | | 13-0 | 33-21-23 | D00674 | | 8 | | D00676 | | 8 | | 115-199 |
| 0129 | 22 | | GA | | 13-0 | 33-21-23 | D00674 | | 9 | | D00676 | | 9 | | 115-199 |
| 0130 | 20 | | GA | | 27-0 | 33-21-51 | D00678 | | 10 | | D41816P | | 4 | | 115-199 |
| 0131 | 20 | | GA | | 9-0 | 33-21-23 | D00678 | | 1 | | SM00131 | | 9 | | 115-199 |
| 0132 | 20 | | GA | | 3-0 | 33-21-23 | D00678 | | 2 | | GD00665 | AC.R | E | | 115-199 |
| 0133 | 24 | | GK | | 9-0 | 33-21-23 | D00678 | | 3 | | SM00133 | | 9 | | 115-199 |
| 0134 | 20 | | GA | | 3-0 | 33-21-23 | D00678 | | 4 | | GD00666 | ST.R | E | | 115-199 |
| 0135 | 22 | | GA | | 13-0 | 33-21-23 | D00678 | | 5 | | D00680 | | 5 | | 115-199 |
| 0136 | 22 | | GA | | 13-0 | 33-21-23 | D00678 | | 6 | | D00680 | | 6 | | 115-199 |
| 0137 | 22 | | GA | | 13-0 | 33-21-23 | D00678 | | 7 | | D00680 | | 7 | | 115-199 |
| 0138 | 22 | | GA | | 13-0 | 33-21-23 | D00678 | | 8 | | D00680 | | 8 | | 115-199 |
| 0139 | 22 | | GA | | 13-0 | 33-21-23 | D00678 | | 9 | | D00680 | | 9 | | 115-199 |
| 0141 | 20 | | GA | | 23-0 | 33-21-23 | D00682 | | 1 | | SM00131 | | 9 | | 115-199 |
| 0142 | 20 | | GA | | 6-0 | 33-21-23 | D00682 | | 2 | | GD00667 | AC.R | E | | 115-199 |
| 0143 | 24 | | GK | | 23-0 | 33-21-23 | D00682 | | 3 | | SM00133 | | 9 | | 115-199 |
| 0144 | 20 | | GA | | 6-0 | 33-21-23 | D00682 | | 4 | | GD00668 | ST.R | E | | 115-199 |
| 0306 | 24 | | GK | | 4-0 | 33-21-23 | D41816P | | 6 | | SM00013 | | 9 | | 001-099 |
| 0309 | 20 | | GA | | 4-0 | 33-21-23 | D41816P | | 9 | | SM00011 | | 9 | | 001-099 |
| 0321 | 20 | | GA | | 12-0 | 33-21-23 | SM00011 | | 9 | | SM00021 | | 9 | | 001-099 |
| 0323 | 24 | | GK | | 12-0 | 33-21-23 | SM00013 | | 9 | | SM00023 | | 9 | | 001-099 |
| 0401 | 20 | | GA | | 11-0 | 33-21-23 | D41816P | | 1 | | SM00121 | | 9 | | 115-199 |
| 0403 | 24 | | GK | | 11-0 | 33-21-23 | D41816P | | 3 | | SM00123 | | 9 | | 115-199 |
| 0421 | 20 | | GA | | 10-0 | 33-21-23 | SM00121 | | 9 | | SM00131 | | 9 | | 115-199 |
| 0423 | 24 | | GK | | 10-0 | 33-21-23 | SM00123 | | 9 | | SM00133 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3610

Page 7 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3632 | 286N3632 | | | OVERHEAD DISC TO EMERGENCY LIGHTS-RIGHT FORWARD AND MID FORWARD | | | | | | | | | | | |
| 0001 | 16 | | GA | | 4-0 | 33-51-12 | D00066 | | 1 | 16 | GD00497 | DC.. | E | | ALL |
| 0002 | 22 | | GA | | 7-0 | 33-51-12 | D00066 | | 2 | | SP01154 | | 9 | | 001-006, 115-199 |
| 0002 | 22 | | GA | | 6-4 | 33-51-12 | D00066 | | 2 | | SP01154 | | 9 | | 007-099 |
| 0003 | 22 | | GA | | 13-0 | 33-51-12 | D00066 | | 3 | | SM00001 | | 9 | | 001-006, 115-199 |
| 0003 | 22 | | GA | | 12-8 | 33-51-12 | D00066 | | 3 | | SM00001 | | 9 | | 007-099 |
| 0004 | 22 | | GA | | 13-0 | 33-51-12 | D00066 | | 4 | | SM00002 | | 9 | | 001-006, 115-199 |
| 0004 | 22 | | GA | | 12-8 | 33-51-12 | D00066 | | 4 | | SM00002 | | 9 | | 007-099 |
| 0005 | 16 | | GA | | 1-0 | 33-51-12 | D00066 | | 5 | 16 | D00066 | | 6 | 16 | 001-006 |
| 0005 | 16 | | GA | | 0-7 | 33-51-12 | D00066 | | 5 | 16 | D00066 | | 6 | 16 | 007-099 |
| 0005 | 22 | | GA | | 1-0 | 33-51-12 | D00066 | | 5 | | D00066 | | 6 | | 115-199 |
| 0006 | 20 | | GA | | 6-0 | 33-51-12 | GD00501 | DC.. | E | | D07506 | | 1 | VY | 001-006 |
| 0006 | 20 | | GA | | 5-2 | 33-51-12 | GD00501 | DC.. | E | | D07506 | | 1 | VY | 007-099 |
| 0006 | 20 | | GA | | 5-0 | 33-51-12 | GD00469 | DC.. | E | | D07510 | | 1 | VY | 115-199 |
| 0007 | 20 | | GA | | 4-0 | 33-51-12 | D00066 | | 7 | | GD02871 | ST.. | E | | 001-006, 115-199 |
| 0007 | 20 | | GA | | 3-5 | 33-51-12 | D00066 | | 7 | | GD02871 | ST.. | E | | 007-099 |
| 0008 | 24 | | GK | | 7-0 | 33-51-12 | D00066 | | 8 | | SP01070 | | 9 | | 001-006, 115-199 |
| 0008 | 24 | | GK | | 6-4 | 33-51-12 | D00066 | | 8 | | SP01070 | | 9 | | 007-099 |
| 0009 | 18 | | GA | | 13-0 | 33-51-12 | D00066 | | 9 | 18 | D04476 | | 1 | VY | ALL |
| 0011 | 20 | | GA | | 8-0 | 33-51-12 | D00066 | | 11 | | D04528 | | 1 | VY | 001-099 |
| 0011 | 20 | | GA | | 8-0 | 33-51-12 | D00066 | | 11 | | D04524 | | 1 | VY | 115-199 |
| 0013 | 22 | | GA | | 10-0 | 33-51-12 | D00066 | | 13 | | D04524 | | 1 | VY | 001-099 |
| 0013 | 22 | | GA | | 10-0 | 33-51-12 | D00066 | | 13 | | D04528 | | 1 | VY | 115-199 |
| 0014 | 22 | | GA | | 17-0 | 33-51-12 | D00066 | | 14 | | D07496 | | 1 | VG | 115-199 |
| 0015 | 20 | | GA | | 16-0 | 33-51-12 | D00066 | | 15 | | D07496 | | 1 | VG | 001-006 |
| 0015 | 20 | | GA | | 15-8 | 33-51-12 | D00066 | | 15 | | D07496 | | 1 | VG | 007-099 |
| 0020 | 22 | | GA | | 2-0 | 33-51-12 | D00066 | | 20 | | D00066 | | 24 | | 001-006, 115-199 |
| 0020 | 22 | | GA | | 0-7 | 33-51-12 | D00066 | | 20 | | D00066 | | 24 | | 007-099 |
| 0033 | 22 | | GA | | 10-0 | 33-51-12 | D40454J | | 3 | | SM00001 | | 9 | | 001-006, 115-199 |
| 0033 | 22 | | GA | | 7-4 | 33-51-12 | D40454J | | 3 | | SM00001 | | 9 | | 007-099 |
| 0034 | 22 | | GA | | 10-0 | 33-51-12 | D40454J | | 4 | | SM00002 | | 9 | | 001-006, 115-199 |
| 0034 | 22 | | GA | | 7-4 | 33-51-12 | D40454J | | 4 | | SM00002 | | 9 | | 007-099 |
| 0040 | 20 | | GA | | 33-0 | SPARE | D40454J | | 5 | | D00070 | CAP | Y | | 001-006, 115-199 |
| 0040 | 20 | | GA | | 32-2 | SPARE | D40454J | | 5 | | D00070 | CAP | Y | | 007-099 |
| 0041 | 20 | | GA | | 33-0 | SPARE | D40454J | | 6 | | D00070 | CAP | Y | | 001-006, 115-199 |
| 0041 | 20 | | GA | | 32-2 | SPARE | D40454J | | 6 | | D00070 | CAP | Y | | 007-099 |
| 0051 | 20 | | GA | | 8-0 | 33-51-12 | D04530 | | 1 | VG | GD00498 | DC.. | E | | 001-006 |
| 0051 | 20 | | GA | | 3-11 | 33-51-12 | D04530 | | 1 | VG | GD00498 | DC.. | E | | 007-099 |
| 0051 | 20 | | GA | | 8-0 | 33-51-12 | D04526 | | 1 | VG | GD00497 | DC.. | E | | 115-199 |
| 0053 | 20 | | GA | | 8-0 | 33-51-12 | D04526 | | 1 | VG | GD00497 | DC.. | E | | 001-006 |

WIRE LIST

D280N032

91-21-11

Section W3630

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|---|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W3632 | 286N3632 | | | OVERHEAD DISC TO EMERGENCY LIGHTS-RIGHT FORWARD AND MID FORWARD (continued) | | | | | | | | | | |
| 0053 | 20 | | GA | 7-3 | 33-51-12 | D04526 | 1 | VG | | GD00497 | DC.. | E | | 007-099 |
| 0053 | 20 | | GA | 4-0 | 33-51-12 | D04530 | 1 | VG | | GD00498 | DC.. | E | | 115-199 |
| 0054 | 20 | | GA | 5-0 | 33-51-12 | D07498 | 1 | VY | | GD00500 | DC.. | E | | 115-199 |
| 0055 | 20 | | GA | 7-0 | 33-51-12 | D07498 | 1 | VY | | GD00500 | DC.. | E | | 001-006 |
| 0055 | 20 | | GA | 3-8 | 33-51-12 | D07498 | 1 | VY | | GD00500 | DC.. | E | | 007-099 |
| 0059 | 20 | | GA | 2-0 | 33-51-12 | D04474 | 1 | VG | | GD00468 | DC.. | E | | 001-006, 115-199 |
| 0059 | 20 | | GA | 1-10 | 33-51-12 | D04474 | 1 | VG | | GD00468 | DC.. | E | | 007-099 |
| 0101 | 16 | | GA | 3-0 | 33-51-13 | D00070 | 1 | 16 | | GD00511 | DC.. | E | | ALL |
| 0102 | 22 | | GA | 9-0 | 33-51-13 | D00070 | 2 | | | SP01586 | | 9 | | 001-006, 115-199 |
| 0102 | 22 | | GA | 8-3 | 33-51-13 | D00070 | 2 | | | SP01586 | | 9 | | 007-099 |
| 0103 | 22 | | GA | 27-0 | 33-51-13 | D00070 | 3 | | | SM00001 | | 9 | | 001-006, 115-199 |
| 0103 | 22 | | GA | 25-11 | 33-51-13 | D00070 | 3 | | | SM00001 | | 9 | | 007-099 |
| 0104 | 22 | | GA | 27-0 | 33-51-13 | D00070 | 4 | | | SM00002 | | 9 | | 001-006, 115-199 |
| 0104 | 22 | | GA | 25-11 | 33-51-13 | D00070 | 4 | | | SM00002 | | 9 | | 007-099 |
| 0105 | 16 | | GA | 1-0 | 33-51-13 | D00070 | 5 | 16 | | D00070 | 6 | 16 | | 001-006 |
| 0105 | 16 | | GA | 0-7 | 33-51-13 | D00070 | 5 | 16 | | D00070 | 6 | 16 | | 007-099 |
| 0105 | 22 | | GA | 1-0 | 33-51-13 | D00070 | 5 | | | D00070 | 6 | | | 115-199 |
| 0107 | 20 | | GA | 4-0 | 33-51-13 | D00070 | 7 | | | GD00510 | ST.. | E | | 001-006, 115-199 |
| 0107 | 20 | | GA | 2-11 | 33-51-13 | D00070 | 7 | | | GD00510 | ST.. | E | | 007-099 |
| 0108 | 24 | | GK | 9-0 | 33-51-13 | D00070 | 8 | | | SP00290 | | 9 | | 001-006, 115-199 |
| 0108 | 24 | | GK | 8-3 | 33-51-13 | D00070 | 8 | | | SP00290 | | 9 | | 007-099 |
| 0109 | 18 | | GA | 16-0 | 33-51-13 | D00070 | 9 | 18 | | D04484 | 1 | VY | | 001-006, 115-199 |
| 0109 | 18 | | GA | 15-0 | 33-51-13 | D00070 | 9 | 18 | | D04484 | 1 | VY | | 007-099 |
| 0110 | 22 | | GA | 9-0 | 33-51-13 | D00070 | 10 | | | SP00302 | | 9 | | 115-199 |
| 0111 | 20 | | GA | 4-0 | 33-51-13 | D00070 | 11 | | | D04540 | 1 | VY | | 001-099 |
| 0111 | 22 | | GA | 4-0 | 33-51-13 | D00070 | 11 | | | D04540 | 1 | VY | | 115-199 |
| 0113 | 20 | | GA | 9-0 | 33-51-13 | D00070 | 13 | | | SP00302 | | 9 | | 001-006 |
| 0113 | 20 | | GA | 8-3 | 33-51-13 | D00070 | 13 | | | SP00302 | | 9 | | 007-099 |
| 0116 | 22 | | GA | 18-0 | 33-51-13 | D00070 | 16 | | | D07500 | 1 | VG | | 001-006 |
| 0116 | 22 | | GA | 17-1 | 33-51-13 | D00070 | 16 | | | D07500 | 1 | VG | | 007-099 |
| 0120 | 22 | | GA | 1-0 | 33-51-13 | D00070 | 20 | | | D00070 | 24 | | | 001-006, 115-199 |
| 0120 | 22 | | GA | 0-7 | 33-51-13 | D00070 | 20 | | | D00070 | 24 | | | 007-099 |
| 0151 | 20 | | GA | 9-0 | 33-51-13 | D04542 | 1 | VG | | GD00503 | DC.. | E | | 001-006, 115-199 |
| 0151 | 20 | | GA | 8-1 | 33-51-13 | D04542 | 1 | VG | | GD00503 | DC.. | E | | 007-099 |
| 0156 | 20 | | GA | 5-0 | 33-51-13 | D07502 | 1 | VY | | GD01838 | DC.. | E | | 001-006 |
| 0156 | 20 | | GA | 4-1 | 33-51-13 | D07502 | 1 | VY | | GD01838 | DC.. | E | | 007-099 |
| 0159 | 20 | | GA | 2-0 | 33-51-13 | D04482 | 1 | VG | | GD00474 | DC.. | E | | 001-006, 115-199 |
| 0159 | 20 | | GA | 1-9 | 33-51-13 | D04482 | 1 | VG | | GD00474 | DC.. | E | | 007-099 |
| 0161 | 24 | | GK | 1-0 | 21-65-11 | SM00003 | | 9 | | D03156 | B | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3630

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|-------|------|------|-------------|---------|-------|------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W3632 | 286N3632 | | | OVERHEAD DISC TO EMERGENCY LIGHTS-RIGHT FORWARD AND MID FORWARD (continued) | | | | | | | | | | | |
| 0162 | 24 | GK | | | 19-0 | 21-61-21 | D40454J | | 10 | | | D02570 | 1 | | 001-006, 115-199 |
| 0162 | 24 | GK | | | 17-4 | 21-61-21 | D40454J | | 10 | | | D02570 | 1 | | 007-099 |
| 0163 | 20 | GA | | | 8-0 | 21-61-21 | D02570 | | 2 | | | GD03662 | AC.. | E | 001-006, 115-199 |
| 0163 | 20 | GA | | | 8-2 | 21-61-21 | D02570 | | 2 | | | GD03662 | AC.. | E | 007-099 |
| 0164 | 20 | GA | | | 8-0 | 21-61-21 | D02570 | | 3 | | | GD03666 | ST.. | E | 001-006, 115-199 |
| 0164 | 20 | GA | | | 7-9 | 21-61-21 | D02570 | | 3 | | | GD03666 | ST.. | E | 007-099 |
| 0165 | 20 | GA | | | 9-0 | 21-65-11 | SM00003 | | 9 | | | GD03720 | DC.. | E | 001-006, 115-199 |
| 0165 | 20 | GA | | | 7-9 | 21-65-11 | SM00003 | | 9 | | | GD03720 | DC.. | E | 007-099 |
| 0166 | 20 | GA | | | 28-0 | 33-51-12 | D00066 | | 16 | | | D07504 | 1 | VG | 001-006 |
| 0166 | 20 | GA | | | 26-11 | 33-51-12 | D00066 | | 16 | | | D07504 | 1 | VG | 007-099 |
| 0166 | 22 | GA | | | 18-4 | 33-51-12 | D00066 | | 16 | | | D07508 | 1 | VG | 115-199 |
| 0501 | 20 | GA | | | 37-0 | 33-51-21 | D00066 | | 10 | | | SP01350 | | 9 | 001-099 |
| 0501 | 20 | GA | | | 41-0 | 33-51-21 | D00066 | | 10 | | | SP01350 | | 9 | 115-199 |
| 0502 | 22 | GA | | | 17-0 | 33-51-21 | D00066 | | 12 | | | D07268 | 1 | VY | 001-006 |
| 0502 | 22 | GA | | | 16-1 | 33-51-21 | D00066 | | 12 | | | D07268 | 1 | VY | 007-099 |
| 0502 | 22 | GA | | | 19-0 | 33-51-21 | D00066 | | 15 | | | D07266 | 1 | VY | 115-199 |
| 0503 | 20 | GA | | | 7-0 | 33-51-21 | D07296 | | 1 | VG | | GD03300 | DC.. | E | 001-006 |
| 0503 | 20 | GA | | | 6-5 | 33-51-21 | D07296 | | 1 | VG | | GD03300 | DC.. | E | 007-099 |
| 0503 | 20 | GA | | | 8-0 | 33-51-21 | D07294 | | 1 | VG | | GD03298 | DC.. | E | 115-199 |
| 0504 | 20 | GA | | | 9-0 | 33-51-21 | D00070 | | 15 | | | SP01348 | | 9 | 115-199 |
| 0505 | 22 | GA | | | 20-0 | 33-51-21 | D00070 | | 16 | | | D07270 | 1 | VY | 115-199 |
| 0506 | 20 | GA | | | 5-0 | 33-51-21 | D07300 | | 1 | VG | | GD03308 | DC.. | E | 001-006 |
| 0506 | 20 | GA | | | 4-10 | 33-51-21 | D07300 | | 1 | VG | | GD03308 | DC.. | E | 007-099 |
| 0506 | 20 | GA | | | 6-0 | 33-51-21 | D07298 | | 1 | VG | | GD03304 | DC.. | E | 115-199 |
| 0510 | 20 | GA | | | 9-0 | 33-51-21 | D00070 | | 10 | | | SP01348 | | 9 | 001-006 |
| 0510 | 20 | GA | | | 8-3 | 33-51-21 | D00070 | | 10 | | | SP01348 | | 9 | 007-099 |
| 0512 | 22 | GA | | | 25-0 | 33-51-21 | D00070 | | 12 | | | D07272 | 1 | VY | 001-006 |
| 0512 | 22 | GA | | | 23-7 | 33-51-21 | D00070 | | 12 | | | D07272 | 1 | VY | 007-099 |
| 0701 | 16 | GA | | | 4-0 | 33-51-14 | D06910 | | 1 | 16 | | GD03998 | DC.. | E | 001-006 |
| 0701 | 16 | GA | | | 3-0 | 33-51-14 | D07994 | | 1 | 16 | | GD04092 | DC.. | E | 007-099 |
| 0702 | 22 | GA | | | 42-0 | 33-51-14 | D06910 | | 2 | | | SP01588 | | 9 | 001-006 |
| 0702 | 22 | GA | | | 39-4 | 33-51-14 | D07994 | | 2 | | | SP01588 | | 9 | 007-099 |
| 0703 | 22 | GA | | | 21-0 | 33-51-14 | D06910 | | 3 | | | SP01894 | | 9 | 001-006 |
| 0703 | 22 | GA | | | 22-3 | 33-51-14 | D07994 | | 3 | | | SP01894 | | 9 | 007-099 |
| 0704 | 22 | GA | | | 21-0 | 33-51-14 | D06910 | | 4 | | | SP01892 | | 9 | 001-006 |
| 0704 | 22 | GA | | | 22-3 | 33-51-14 | D07994 | | 4 | | | SP01892 | | 9 | 007-099 |
| 0705 | 16 | GA | | | 1-0 | 33-51-14 | D06910 | | 5 | 16 | | D06910 | 6 | 16 | 001-006 |
| 0705 | 16 | GA | | | 0-7 | 33-51-14 | D07994 | | 5 | 16 | | D07994 | 6 | 16 | 007-099 |
| 0707 | 20 | GA | | | 5-0 | 33-51-14 | D06910 | | 7 | | | GD04004 | ST.. | E | 001-006 |

WIRE LIST

D280N032

91-21-11

Section W3630

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|--|------------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3632 | 286N3632 | | | | OVERHEAD DISC TO EMERGENCY LIGHTS-RIGHT FORWARD AND MID FORWARD (continued) | | | | | | | | | | | | |
| 0707 | 20 | | GA | | 3-5 | 33-51-14 | D07994 | | 7 | | | GD04094 | ST.. | E | | 007-099 | |
| 0708 | 24 | | GK | | 20-0 | 33-51-14 | D06910 | | 8 | | | SP00290 | | 9 | | 001-006 | |
| 0708 | 24 | | GK | | 22-3 | 33-51-14 | D07994 | | 8 | | | SP00290 | | 9 | | 007-099 | |
| 0710 | 20 | | GA | | 38-0 | 33-51-22 | D06910 | | 10 | | | SP01354 | | 9 | | 001-006 | |
| 0710 | 20 | | GA | | 33-0 | 33-51-22 | D07994 | | 10 | | | SP01354 | | 9 | | 007-099 | |
| 0711 | 16 | | GA | | 26-0 | SPARE | D06910 | | 11 | 16 | | D06916 | 1 | VY | | 001-006 | |
| 0711 | 16 | | GA | | 27-11 | SPARE | D07994 | | 11 | 16 | | D06916 | 1 | VY | | 007-099 | |
| 0712 | 16 | | GA | | 26-0 | SPARE | D06910 | | 12 | 16 | | D06920 | 1 | VY | | 001-006 | |
| 0712 | 16 | | GA | | 27-11 | SPARE | D07994 | | 12 | 16 | | D06920 | 1 | VY | | 007-099 | |
| 0713 | 16 | | GA | | 38-0 | SPARE | D06910 | | 13 | 16 | | D06854 | 1 | VY | | 001-006 | |
| 0713 | 16 | | GA | | 35-6 | SPARE | D07994 | | 13 | 16 | | D06854 | 1 | VY | | 007-099 | |
| 0716 | 22 | | GA | | 17-0 | 33-51-14 | D06910 | | 16 | | | D07520 | 1 | VG | | 001-006 | |
| 0716 | 22 | | GA | | 10-6 | 33-51-14 | D07994 | | 16 | | | D07520 | 1 | VG | | 007-099 | |
| 0720 | 20 | | GA | | 1-0 | 33-51-14 | D06910 | | 20 | | | D06910 | 24 | | | 001-006 | |
| 0720 | 20 | | GA | | 0-7 | 33-51-14 | D07994 | | 20 | | | D07994 | 24 | | | 007-099 | |
| 0751 | 20 | | GA | | 3-0 | SPARE | D06918 | | 1 | VG | | GD04014 | DC.. | E | | 001-006 | |
| 0751 | 20 | | GA | | 2-11 | SPARE | D06918 | | 1 | VG | | GD04014 | DC.. | E | | 007-099 | |
| 0752 | 20 | | GA | | 3-0 | SPARE | D06922 | | 1 | VG | | GD04014 | DC.. | E | | 001-099 | |
| 0753 | 20 | | GA | | 3-0 | SPARE | D06856 | | 1 | VG | | GD03936 | DC.. | E | | 001-006 | |
| 0753 | 20 | | GA | | 2-2 | SPARE | D06856 | | 1 | VG | | GD03936 | DC.. | E | | 007-099 | |
| 0756 | 20 | | GA | | 8-0 | 33-51-14 | D07522 | | 1 | VY | | GD00506 | DC.. | E | | 001-006 | |
| 0756 | 20 | | GA | | 7-0 | 33-51-14 | D07522 | | 1 | VY | | GD00506 | DC.. | E | | 007-099 | |
| 2001B | 24 | | GL | AA | 18-0 | 21-65-11 | D40454J | | 7 | | | D03156 | A | | | 001-006, 115-199 | |
| 2001B | 24 | | GL | AA | 16-7 | 21-65-11 | D40454J | | 7 | | | D03156 | A | | | 007-099 | |
| 2001R | 24 | | GL | AA | 0-0 | 21-65-11 | D40454J | | 8 | | | SM00003 | | 9 | | ALL | |
| W3634 | 286N3634 | | | | INTERIOR EMERGENCY LIGHTS-RIGHT AFT AND MID AFT | | | | | | | | | | | | |
| 0001 | 16 | | GA | | 3-0 | 33-51-14 | D00074 | | 1 | 16 | | GD00525 | DC.. | E | | ALL | |
| 0002 | 22 | | GA | | 22-3 | 33-51-14 | D00074 | | 2 | | | SP01588 | | 9 | | 001-099 | |
| 0002 | 22 | | GA | | 21-3 | 33-51-14 | D00074 | | 2 | | | SP01588 | | 9 | | 115-199 | |
| 0003 | 22 | | GA | | 11-2 | 33-51-14 | D00074 | | 3 | | | SM00001 | | 9 | | ALL | |
| 0004 | 22 | | GA | | 11-2 | 33-51-14 | D00074 | | 4 | | | SM00002 | | 9 | | ALL | |
| 0005 | 16 | | GA | | 0-7 | 33-51-14 | D00074 | | 5 | 16 | | D00074 | 6 | 16 | | 001-099 | |
| 0005 | 22 | | GA | | 0-7 | 33-51-14 | D00074 | | 5 | | | D00074 | 6 | | | 115-199 | |
| 0007 | 20 | | GA | | 3-6 | 33-51-14 | D00074 | | 7 | | | GD00524 | ST.. | E | | ALL | |
| 0008 | 24 | | GK | | 22-3 | 33-51-14 | D00074 | | 8 | | | SP00286 | | 9 | | 001-099 | |
| 0008 | 24 | | GK | | 21-3 | 33-51-14 | D00074 | | 8 | | | SP00286 | | 9 | | 115-199 | |
| 0009 | 18 | | GA | | 25-0 | 33-51-14 | D00074 | | 9 | 18 | | D04492 | 1 | VY | | ALL | |
| 0010 | 20 | | GA | | 33-9 | 33-51-22 | D00074 | | 10 | | | SP01358 | | 9 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3630

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3634 | 286N3634 | | | INTERIOR EMERGENCY LIGHTS-RIGHT AFT AND MID AFT (continued) | | | | | | | | | | | |
| 0011 | 20 | GA | | | 4-0 | 33-51-14 | D00074 | 11 | | | D04600 | 1 | VY | | 001-099 |
| 0011 | 20 | GA | | | 8-4 | 33-51-14 | D00074 | 11 | | | SP01370 | | 9 | | 115-199 |
| 0014 | 20 | GA | | | 31-1 | 33-51-14 | D00074 | 14 | | | D07544 | 1 | VG | | 001-099 |
| 0015 | 22 | GA | | | 17-5 | 33-51-14 | D00074 | 15 | | | D07540 | 1 | VG | | 001-099 |
| 0015 | 22 | GA | | | 31-1 | 33-51-14 | D00074 | 15 | | | D07544 | 1 | VG | | 115-199 |
| 0016 | 22 | GA | | | 15-4 | 33-51-14 | D00074 | 16 | | | D07556 | 1 | VG | | 001-099 |
| 0020 | 22 | GA | | | 0-7 | 33-51-14 | D00074 | 20 | | | D00074 | 24 | | | ALL |
| 0030 | 22 | GA | | | 48-11 | 33-51-14 | SP01892 | | 9 | | SM00002 | | 9 | | 001-099 |
| 0031 | 22 | GA | | | 29-3 | 33-51-14 | D40456J | 11 | | | SP01894 | | 9 | | 001-099 |
| 0033 | 22 | GA | | | 75-1 | 33-51-14 | D40456J | 3 | | | SM00001 | | 9 | | ALL |
| 0034 | 22 | GA | | | 75-1 | 33-51-14 | D40456J | 4 | | | SM00002 | | 9 | | ALL |
| 0040 | 20 | GA | | | 112-8 | SPARE | D40456J | 5 | | | D00078 | CAP | Y | | ALL |
| 0041 | 20 | GA | | | 112-8 | SPARE | D40456J | 6 | | | D00078 | CAP | Y | | ALL |
| 0050 | 20 | GA | | | 4-0 | 33-51-14 | D04606 | 1 | VG | | GD02876 | DC.. | E | | 001-099 |
| 0051 | 20 | GA | | | 6-1 | 33-51-14 | D04602 | 1 | VG | | GD00518 | DC.. | E | | 001-099 |
| 0054 | 20 | GA | | | 6-4 | 33-51-14 | D07546 | 1 | VY | | GD00487 | DC.. | E | | 001-099 |
| 0055 | 20 | GA | | | 6-1 | 33-51-14 | D07542 | 1 | VY | | GD04028 | DC.. | E | | 001-099 |
| 0055 | 20 | GA | | | 6-4 | 33-51-14 | D07546 | 1 | VY | | GD00487 | DC.. | E | | 115-199 |
| 0056 | 20 | GA | | | 3-7 | 33-51-14 | D07558 | 1 | VY | | GD00520 | DC.. | E | | 001-099 |
| 0059 | 20 | GA | | | 3-0 | 33-51-14 | D04490 | 1 | VG | | GD00482 | DC.. | E | | ALL |
| 0101 | 16 | GA | | | 3-0 | 33-51-15 | D00078 | 1 | 16 | | GD00527 | DC.. | E | | ALL |
| 0102 | 22 | GA | | | 49-8 | 33-51-15 | D00078 | 2 | | | SP01588 | | 9 | | 001-099 |
| 0102 | 22 | GA | | | 48-8 | 33-51-15 | D00078 | 2 | | | SP01588 | | 9 | | 115-199 |
| 0103 | 22 | GA | | | 38-7 | 33-51-15 | D00078 | 3 | | | SM00001 | | 9 | | ALL |
| 0104 | 22 | GA | | | 38-7 | 33-51-15 | D00078 | 4 | | | SM00002 | | 9 | | ALL |
| 0105 | 16 | GA | | | 0-7 | 33-51-15 | D00078 | 5 | 16 | | D00078 | 6 | 16 | | 001-099 |
| 0105 | 22 | GA | | | 0-7 | 33-51-15 | D00078 | 5 | | | D00078 | 6 | | | 115-199 |
| 0107 | 20 | GA | | | 2-11 | 33-51-15 | D00078 | 7 | | | GD00526 | ST.. | E | | ALL |
| 0108 | 24 | GK | | | 11-2 | 33-51-15 | D00078 | 8 | | | SP00294 | | 9 | | ALL |
| 0109 | 18 | GA | | | 12-0 | 33-51-15 | D00078 | 9 | 18 | | D04508 | 1 | VY | | ALL |
| 0110 | 20 | GA | | | 11-2 | 33-51-22 | D00078 | 10 | | | SP01360 | | 9 | | 001-099 |
| 0111 | 20 | GA | | | 7-8 | 33-51-15 | D00078 | 11 | | | D04564 | 1 | VY | | 001-099 |
| 0111 | 22 | GA | | | 7-8 | 33-51-15 | D00078 | 11 | | | D04564 | 1 | VY | | 115-199 |
| 0112 | 22 | GA | | | 14-9 | 33-51-22 | D00078 | 12 | | | D07284 | 1 | VY | | 001-099 |
| 0113 | 20 | GA | | | 5-4 | 33-51-15 | D00078 | 13 | | | SP00306 | | 9 | | 001-099 |
| 0113 | 20 | GA | | | 35-0 | 33-51-15 | D00078 | 13 | | | D07556 | 1 | VG | | 115-199 |
| 0114 | 22 | GA | | | 29-0 | 33-51-15 | D00078 | 14 | | | D07560 | 1 | VG | | 115-199 |
| 0116 | 22 | GA | | | 19-3 | 33-51-15 | D00078 | 16 | | | D07560 | 1 | VG | | 001-099 |
| 0120 | 22 | GA | | | 0-7 | 33-51-15 | D00078 | 20 | | | D00078 | 24 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3630

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3634 | 286N3634 | | | INTERIOR EMERGENCY LIGHTS-RIGHT AFT AND MID AFT (continued) | | | | | | | | | | | |
| 0151 | 20 | | GA | | 3-4 | 33-51-15 | D04566 | 1 | VG | | GD00522 | DC.. | E | | ALL |
| 0153 | 20 | | GA | | 3-7 | 33-51-15 | D07558 | 1 | VY | | GD00520 | DC.. | E | | 115-199 |
| 0154 | 20 | | GA | | 3-8 | 33-51-15 | D07562 | 1 | VY | | GD03698 | DC.. | E | | 115-199 |
| 0156 | 20 | | GA | | 3-8 | 33-51-15 | D07562 | 1 | VY | | GD03698 | DC.. | E | | 001-099 |
| 0159 | 18 | | GA | | 3-8 | 33-51-15 | D04506 | 1 | VG | | GD00488 | DC.. | E | | ALL |
| 0161 | 24 | | GK | | 1-0 | 21-65-11 | SM00003 | | 9 | | D03158 | B | | | ALL |
| 0162 | 24 | | GK | | 73-2 | 21-61-31 | D40456J | 10 | | | D02584 | 1 | | | ALL |
| 0163 | 20 | | GA | | 7-10 | 21-61-31 | D02584 | 2 | | | GD03664 | AC.. | E | | 001-099 |
| 0163 | 20 | | GA | | 7-11 | 21-61-31 | D02584 | 2 | | | GD03664 | AC.. | E | | 115-199 |
| 0164 | 20 | | GA | | 7-7 | 21-61-31 | D02584 | 3 | | | GD03668 | ST.. | E | | 001-099 |
| 0164 | 20 | | GA | | 7-8 | 21-61-31 | D02584 | 3 | | | GD03668 | ST.. | E | | 115-199 |
| 0165 | 20 | | GA | | 7-10 | 21-65-11 | SM00003 | | 9 | | GD03708 | DC.. | E | | 001-099 |
| 0165 | 20 | | GA | | 14-0 | 21-65-11 | SM00003 | | 9 | | GD03708 | DC.. | E | | 115-199 |
| 0501 | 16 | | GA | | 3-0 | 33-51-14 | D07290 | 1 | 16 | | GD02564 | DC.. | E | | ALL |
| 0502 | 22 | | GA | | 15-10 | 33-51-14 | D07290 | 2 | | | SP01588 | | 9 | | 001-099 |
| 0502 | 22 | | GA | | 14-10 | 33-51-14 | D07290 | 2 | | | SP01588 | | 9 | | 115-199 |
| 0503 | 22 | | GA | | 53-2 | 33-51-14 | D07290 | 3 | | | SP01894 | | 9 | | 001-099 |
| 0503 | 22 | | GA | | 78-10 | 33-51-14 | D07290 | 3 | | | D40456J | 11 | | | 115-199 |
| 0504 | 22 | | GA | | 8-5 | 33-51-14 | D07290 | 4 | | | SM00002 | | 9 | | ALL |
| 0505 | 16 | | GA | | 0-7 | 33-51-14 | D07290 | 5 | 16 | | D07290 | 6 | 16 | | 001-099 |
| 0505 | 22 | | GA | | 0-7 | 33-51-14 | D07290 | 5 | | | D07290 | 6 | | | 115-199 |
| 0507 | 20 | | GA | | 3-3 | 33-51-14 | D07290 | 7 | | | GD02562 | ST.. | E | | ALL |
| 0508 | 24 | | GK | | 15-10 | 33-51-14 | D07290 | 8 | | | SP00286 | | 9 | | 001-099 |
| 0508 | 24 | | GK | | 14-10 | 33-51-14 | D07290 | 8 | | | SP00286 | | 9 | | 115-199 |
| 0509 | 22 | | GA | | 35-3 | 33-51-14 | D07290 | 9 | | | D07602 | 1 | VG | | 115-199 |
| 0510 | 20 | | GA | | 26-9 | 33-51-22 | D07290 | 10 | | | SP01356 | | 9 | | 001-099 |
| 0510 | 20 | | GA | | 44-5 | 33-51-14 | D07290 | 10 | | | D07532 | 1 | VG | | 115-199 |
| 0511 | 20 | | GA | | 38-0 | 33-51-14 | D07290 | 11 | | | D07528 | 1 | VG | | 115-199 |
| 0512 | 20 | | GA | | 26-9 | 33-51-22 | D07290 | 12 | | | SP01356 | | 9 | | 115-199 |
| 0513 | 18 | | GA | | 12-1 | 33-51-14 | D07290 | 13 | 18 | | D04604 | 1 | VY | | 001-099 |
| 0513 | 20 | | GA | | 26-9 | 33-51-22 | D07290 | 13 | | | SP01354 | | 9 | | 115-199 |
| 0515 | 22 | | GA | | 20-8 | 33-51-14 | D07290 | 15 | | | D04600 | 1 | VY | | 115-199 |
| 0516 | 20 | | GA | | 35-2 | 33-51-14 | D07290 | 16 | | | D07602 | 1 | VG | | 001-099 |
| 0520 | 22 | | GA | | 0-7 | 33-51-14 | D07290 | 20 | | | D07290 | 24 | | | ALL |
| 0522 | 22 | | GA | | 25-6 | 33-51-22 | D00074 | 12 | | | D07288 | 1 | VY | | 001-099 |
| 0522 | 22 | | GA | | 22-4 | 33-51-22 | D00074 | 12 | | | D07286 | 1 | VY | | 115-199 |
| 0524 | 20 | | GA | | 33-9 | 33-51-22 | D00074 | 14 | | | SP01358 | | 9 | | 115-199 |
| 0525 | 20 | | GA | | 6-11 | 33-51-22 | D07316 | 1 | VG | | GD03328 | DC.. | E | | 001-099 |
| 0525 | 20 | | GA | | 7-7 | 33-51-22 | D07314 | 1 | VG | | GD03326 | DC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3630

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3634 | 286N3634 | | | INTERIOR EMERGENCY LIGHTS-RIGHT AFT AND MID AFT (continued) | | | | | | | | | | | |
| 0527 | 22 | | GA | | 15-7 | 33-51-22 | D00078 | 16 | | | D07282 | 1 | VY | | 115-199 |
| 0528 | 20 | | GA | | 11-2 | 33-51-22 | D00078 | 12 | | | SP01360 | | 9 | | 115-199 |
| 0529 | 20 | | GA | | 4-6 | 33-51-22 | D07312 | 1 | VG | | GD03324 | DC.. | E | | 001-099 |
| 0529 | 20 | | GA | | 4-8 | 33-51-22 | D07310 | 1 | VG | | GD03322 | DC.. | E | | 115-199 |
| 0550 | 20 | | GA | | 6-5 | 33-51-14 | D07534 | 1 | VY | | GD00476 | DC.. | E | | 115-199 |
| 0551 | 20 | | GA | | 10-8 | 33-51-14 | D07530 | 1 | VY | | GD00477 | DC.. | E | | 115-199 |
| 0555 | 20 | | GA | | 6-1 | 33-51-14 | D04602 | 1 | VG | | GD00518 | DC.. | E | | 115-199 |
| 0556 | 20 | | GA | | 6-5 | 33-51-14 | D07604 | 1 | VY | | GD00507 | DC.. | E | | 001-099 |
| 0559 | 20 | | GA | | 6-5 | 33-51-14 | D07604 | 1 | VY | | GD00507 | DC.. | E | | 115-199 |
| 2001B | 24 | | GL | AA | 72-6 | 21-65-11 | D40456J | 7 | | | D03158 | A | | | ALL |
| 2001R | 24 | | GL | AA | 0-0 | 21-65-11 | D40456J | 8 | | | SM00003 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3630

Page 7 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3644 | 286N3644 | | | | GALLEY 1A LIGHTING AND CONTROL | | | | | | | | | | | | |
| 0001 | 22 | | GA | | 22-2 | 33-27-11 | D00970 | | | | 1 | | SP01316 | | 9 | | 001-099 |
| 0002 | 20 | | GA | | 3-10 | 33-27-11 | D00970 | | | | 2 | | GD01441 | AC.. | E | | 001-099 |
| 0002 | 22 | | GA | | 47-0 | 25-31-21 | D40664P | | | | 1 | | D01660 | | 4 | | 115-199 |
| 0003 | 22 | | GA | | 8-10 | 33-27-11 | D00970 | | | | 3 | | D01652 | | 11 | | 001-099 |
| 0003 | 22 | | GA | | 47-0 | 25-31-21 | D40664P | | | | 2 | | D01660 | | 5 | | 115-199 |
| 0004 | 20 | | GA | | 3-10 | 33-27-11 | D00970 | | | | 4 | | GD01442 | ST.. | E | | 001-099 |
| 0004 | 22 | | GA | | 47-0 | 25-31-21 | D40664P | | | | 3 | | D01660 | | 6 | | 115-199 |
| 0005 | 22 | | GA | | 8-10 | 33-27-11 | D00970 | | | | 5 | | D01652 | | 3 | | 001-099 |
| 0005 | 22 | | GA | | 47-0 | 25-31-21 | D40664P | | | | 4 | | D01660 | | 7 | | 115-199 |
| 0006 | 22 | | GA | | 45-3 | 33-27-11 | D00970 | | | | 6 | | D40664P | | 4 | | 001-099 |
| 0007 | 22 | | GA | | 20-5 | 33-27-11 | D01652 | | | | 12 | | SP01312 | | 9 | | 001-099 |
| 0008 | 22 | | GA | | 20-5 | 33-27-11 | D01652 | | | | 8 | | SP01314 | | 9 | | 001-099 |
| 0015 | 22 | | GA | | 50-0 | 33-27-21 | D40664P | | | | 17 | | SP01824 | | 9 | | 115-199 |
| 0016 | 22 | | GA | | 50-0 | 33-27-21 | D40664P | | | | 9 | | SP01820 | | 9 | | 115-199 |
| 0017 | 22 | | GA | | 50-0 | 33-27-21 | D40664P | | | | 10 | | SP01822 | | 9 | | 115-199 |
| 0018 | 22 | | GA | | 9-0 | 33-27-21 | D02852 | | | | 5 | | D01660 | | 3 | | 001-099 |
| 0018 | 22 | | GA | | 10-0 | 33-27-21 | D01660 | | | | 3 | | D02852 | | 5 | | 115-199 |
| 0019 | 22 | | GA | | 9-0 | 33-27-21 | D02852 | | | | 3 | | D01660 | | 11 | | 001-099 |
| 0019 | 22 | | GA | | 10-0 | 33-27-21 | D01660 | | | | 11 | | D02852 | | 3 | | 115-199 |
| 0020 | 20 | | GA | | 6-5 | 33-27-21 | D02852 | | | | 4 | | GD01444 | ST.. | E | | 001-099 |
| 0020 | 22 | | GA | | 6-8 | 33-27-21 | D02852 | | | | 4 | | GD01444 | ST.. | E | | 115-199 |
| 0021 | 20 | | GA | | 6-5 | 33-27-21 | D02852 | | | | 2 | | GD01443 | AC.. | E | | 001-099 |
| 0021 | 22 | | GA | | 6-8 | 33-27-21 | D02852 | | | | 2 | | GD01443 | AC.. | E | | 115-199 |
| 0029 | 22 | | GA | | 32-0 | 33-27-11 | D00970 | | | | 6 | | D40664P | | 13 | | 115-199 |
| 0030 | 20 | | GA | | 32-0 | 33-27-11 | D00970 | | | | 1 | | D40664P | | 15 | | 115-199 |
| 0031 | 22 | | GA | | 4-0 | 33-27-11 | D00970 | | | | 4 | | GD01442 | ST.. | E | | 115-199 |
| 0032 | 22 | | GA | | 4-0 | 33-27-11 | D00970 | | | | 2 | | GD01441 | AC.. | E | | 115-199 |
| 0034 | 22 | | GA | | 32-0 | 33-27-11 | D40664P | | | | 11 | | SP01074 | | 9 | | 115-199 |
| 0036 | 22 | | GA | | 9-0 | 33-27-11 | D00970 | | | | 5 | | SP01078 | | 9 | | 115-199 |
| 0037 | 22 | | GA | | 9-0 | 33-27-11 | D00970 | | | | 3 | | SP01080 | | 9 | | 115-199 |
| 0038 | 22 | | GA | | 15-5 | 33-27-21 | D01660 | | | | 12 | | SP01318 | | 9 | | 001-099 |
| 0038 | 22 | | GA | | 8-0 | 33-27-21 | D01660 | | | | 12 | | SP01820 | | 9 | | 115-199 |
| 0039 | 22 | | GA | | 15-5 | 33-27-21 | D01660 | | | | 8 | | SP01320 | | 9 | | 001-099 |
| 0039 | 22 | | GA | | 8-0 | 33-27-21 | D01660 | | | | 8 | | SP01822 | | 9 | | 115-199 |
| 0040 | 22 | | GA | | 18-11 | 33-27-21 | D02852 | | | | 1 | | SP01322 | | 9 | | 001-099 |
| 0040 | 22 | | GA | | 8-0 | 33-27-21 | D02852 | | | | 1 | | SP01824 | | 9 | | 115-199 |
| 0047 | 22 | | GA | | 43-6 | 25-31-11 | D40664P | | | | 1 | | D01652 | | 4 | | 001-099 |
| 0048 | 22 | | GA | | 43-6 | 25-31-11 | D40664P | | | | 2 | | D01652 | | 5 | | 001-099 |
| 0049 | 22 | | GA | | 43-6 | 25-31-11 | D40664P | | | | 3 | | D01652 | | 6 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3640

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--|-------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3644 | 286N3644 | | | GALLEY 1A LIGHTING AND CONTROL (continued) | | | | | | | | | | | | |
| 0050 | 22 | | GA | | 43-6 | 25-31-11 | D40664P | | 7 | | | D01652 | | 7 | | 001-099 |
| 0059 | 22 | | GA | | 44-0 | SPARE | D40664P | | 13 | | | D01660 | | 9 | | 001-099 |
| 0060 | 22 | | GA | | 44-0 | SPARE | D40664P | | 14 | | | D01660 | | 10 | | 001-099 |
| W3648 | 286N3648 | | | GALLEY POWER-FORWARD GALLEYS | | | | | | | | | | | | |
| 0001 | 10 | | HA | | 4-0 | 25-31-11 | D05606 | | A | | | SM00001 | | 9 | | 115-199 |
| 0002 | 10 | | HA | | 4-0 | 25-31-11 | D05606 | | B | | | SM00002 | | 9 | | 115-199 |
| 0003 | 10 | | HA | | 4-0 | 25-31-11 | D05606 | | C | | | SM00003 | | 9 | | 115-199 |
| 0004 | 08 | | HA | | 4-0 | 25-31-11 | D05606 | | D | | | GD01226 | AC.. | E | | 115-199 |
| 0005 | 10 | | HA | | 28-0 | 25-31-13 | TB5050 | | 4 | E | | SM00001 | | 9 | | 115-199 |
| 0006 | 10 | | HA | | 28-0 | 25-31-13 | TB5050 | | 5 | E | | SM00002 | | 9 | | 115-199 |
| 0007 | 10 | | HA | | 28-0 | 25-31-13 | TB5050 | | 6 | E | | SM00003 | | 9 | | 115-199 |
| 0008 | 10 | | HA | | 7-0 | 25-31-13 | D06790 | | A | | | SM00001 | | 9 | | 115-199 |
| 0009 | 10 | | HA | | 7-0 | 25-31-13 | D06790 | | B | | | SM00002 | | 9 | | 115-199 |
| 0010 | 10 | | HA | | 7-0 | 25-31-13 | D06790 | | C | | | SM00003 | | 9 | | 115-199 |
| 0011 | 08 | | HA | | 2-11 | 25-31-13 | D06790 | | D | | | GD01739 | AC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3640

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--|-------------|----|----|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3650 286N3650 P32 OR P37 TO GALLEY 1A AC POWER | | | | | | | | | | | | | | | |
| 0001 | 08 | | HA | | 2-10 | 25-31-11 | D01650 | | A | | SM00001 | | GX | | 001-099 |
| 0001 | 10 | | HA | | 32-0 | 25-31-11 | D01650 | | A | | TB5070 | 10 | E | | 115-199 |
| 0002 | 08 | | HA | | 3-1 | 25-31-11 | D01650 | | B | | SM00002 | | GX | | 001-099 |
| 0002 | 10 | | HA | | 32-0 | 25-31-11 | D01650 | | B | | TB5070 | 11 | E | | 115-199 |
| 0003 | 08 | | HA | | 3-4 | 25-31-11 | D01650 | | C | | SM00003 | | GX | | 001-099 |
| 0003 | 10 | | HA | | 32-0 | 25-31-11 | D01650 | | C | | TB5070 | 12 | E | | 115-199 |
| 0004 | 08 | | HA | | 1-9 | 25-31-11 | D01650 | | D | | GD01226 | AC.. | E | | 001-099 |
| 0004 | 10 | | HA | | 2-0 | 25-31-11 | D01650 | | D | | GD01226 | AC.. | E | | 115-199 |
| 0005 | 06 | | 43 | | 28-11 | 25-31-11 | M00546 | A2 | H6 | | SM00001 | | GX | | 001-099 |
| 0006 | 06 | | 43 | | 28-6 | 25-31-11 | M00546 | B2 | H6 | | SM00002 | | GX | | 001-099 |
| 0007 | 06 | | 43 | | 28-2 | 25-31-11 | M00546 | C2 | H6 | | SM00003 | | GX | | 001-099 |
| W3658 286N3658 P32 TO GALLEY NO. 2A AC POWER | | | | | | | | | | | | | | | |
| 0001 | 08 | | HA | | 4-0 | 25-31-21 | SM00001 | | GX | | D01658 | A | | | 115-199 |
| 0002 | 08 | | HA | | 4-0 | 25-31-21 | SM00002 | | GX | | D01658 | B | | | 115-199 |
| 0003 | 08 | | HA | | 4-0 | 25-31-21 | SM00003 | | GX | | D01658 | C | | | 115-199 |
| 0004 | 08 | | HA | | 4-0 | 25-31-21 | D01658 | | D | | GD01300 | AC.R | E | | 115-199 |
| 0005 | 06 | | 43 | | 43-0 | 25-31-21 | M00225 | A2 | H6 | | SM00001 | | GX | | 115-199 |
| 0006 | 06 | | 43 | | 43-0 | 25-31-21 | M00225 | B2 | H6 | | SM00002 | | GX | | 115-199 |
| 0007 | 06 | | 43 | | 43-0 | 25-31-21 | M00225 | C2 | H6 | | SM00003 | | GX | | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W3650
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|----------------------------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|----|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3660 | 286N3660 | | | | P37 TO GALLEY NO. 2A AC POWER | | | | | | | | | | | | |
| 0001 | 10 | | HA | | 46-0 | 25-31-21 | TB5070 | | CAP | Y | | | D01658 | | A | | 001-099 |
| 0002 | 10 | | HA | | 46-0 | 25-31-21 | TB5070 | | CAP | Y | | | D01658 | | B | | 001-099 |
| 0003 | 10 | | HA | | 46-0 | 25-31-21 | TB5070 | | CAP | Y | | | D01658 | | C | | 001-099 |
| 0004 | 10 | | HA | | 3-0 | 25-31-21 | D01658 | | | D | | | GD01300 | | AC.. | E | 001-099 |
| W3662 | 286N3662 | | | | P32 OR P37 TO GALLEY 2B AC POWER | | | | | | | | | | | | |
| 0001 | 12 | | HA | | 50-0 | 25-31-23 | D01662 | | | A | | | TB5070 | | 7 | E | 115-199 |
| 0002 | 12 | | HA | | 50-0 | 25-31-23 | D01662 | | | B | | | TB5070 | | 8 | E | 115-199 |
| 0003 | 12 | | HA | | 50-0 | 25-31-23 | D01662 | | | C | | | TB5070 | | 9 | E | 115-199 |
| 0004 | 12 | | HA | | 3-0 | 25-31-23 | D01662 | | | D | | | GD01240 | | AC.. | E | 115-199 |
| W3668 | 286N3668 | | | | P37 TO AFT GALLEY AREA | | | | | | | | | | | | |
| 0001 | 10 | | HA | | 3-7 | 25-31-31 | D01666 | | | A | | | SM00001 | | | GX | 001-099 |
| 0002 | 10 | | HA | | 3-7 | 25-31-31 | D01666 | | | B | | | SM00002 | | | GX | 001-099 |
| 0003 | 10 | | HA | | 3-7 | 25-31-31 | D01666 | | | C | | | SM00003 | | | GX | 001-099 |
| 0004 | 10 | | HA | | 3-7 | 25-31-31 | D01666 | | | D | | | GD01738 | | AC.. | E | 001-099 |
| 0005 | 08 | | 43 | | 136-10 | 25-31-31 | TB5070 | | 10 | BS | | | SM00001 | | | GX | 001-099 |
| 0006 | 08 | | 43 | | 136-10 | 25-31-31 | TB5070 | | 11 | BS | | | SM00002 | | | GX | 001-099 |
| 0007 | 08 | | 43 | | 136-10 | 25-31-31 | TB5070 | | 12 | BS | | | SM00003 | | | GX | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3660

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3670 | 286N3670 | | | GALLEY POWER -FEEDER FROM P37 | | | | | | | | | | | |
| 0008 | 10 | | HA | | 2-6 | 25-31-13 | D01654 | | A | | SM00004 | | GX | | 001-099 |
| 0009 | 10 | | HA | | 2-6 | 25-31-13 | D01654 | | B | | SM00005 | | GX | | 001-099 |
| 0010 | 10 | | HA | | 2-6 | 25-31-13 | D01654 | | C | | SM00006 | | GX | | 001-099 |
| 0011 | 10 | | HA | | 2-9 | 25-31-13 | D01654 | | D | | GD01739 | AC.. | E | | 001-099 |
| 0012 | 08 | | 43 | | 26-0 | 25-31-13 | TB5070 | 1 | BS | | SM00004 | | GX | | 001-099 |
| 0013 | 08 | | 43 | | 26-0 | 25-31-13 | TB5070 | 2 | BS | | SM00005 | | GX | | 001-099 |
| 0014 | 08 | | 43 | | 26-0 | 25-31-13 | TB5070 | 3 | BS | | SM00006 | | GX | | 001-099 |
| W3672 | 286N3672 | | | MISC. LIGHTING ,RIGHT | | | | | | | | | | | |
| 0001 | 18 | | GA | | 32-2 | 33-44-11 | D00040 | 1 | | | D41302P | 1 | 18 | | 001-099 |
| 0001 | 18 | | GA | | 32-0 | 33-44-11 | D00040 | 1 | | | D41302P | 1 | 18 | | 115-199 |
| 0002 | 20 | | GA | | 5-5 | 33-44-11 | D00040 | 2 | | | GD01487 | AC.. | E | | 001-099 |
| 0002 | 20 | | GA | | 5-0 | 33-44-11 | D00040 | 2 | | | GD01487 | AC.. | E | | 115-199 |
| 0003 | 18 | | GA | | 5-5 | 33-44-11 | D00040 | 3 | | | GD01488 | ST.. | E | | 001-099 |
| 0003 | 18 | | GA | | 5-0 | 33-44-11 | D00040 | 3 | 18 | | GD01488 | ST.. | E | | 115-199 |
| 0004 | 22 | | GA | | 45-5 | 38-14-11 | N10005 | 2 | B | | D41302P | 17 | | | 001-099 |
| 0004 | 22 | | GA | | 47-0 | 38-14-11 | N10005 | 2 | B | | D41302P | 17 | | | 115-199 |
| 0005 | 22 | | GA | | 45-5 | 38-14-11 | N10005 | 1 | B | | D41302P | 18 | | | 001-099 |
| 0005 | 22 | | GA | | 47-0 | 38-14-11 | N10005 | 1 | B | | D41302P | 18 | | | 115-199 |
| 0006 | 22 | | GA | | 114-6 | 23-42-11 | D04522 | 1 | | | D41700P | 3 | | | 001-099 |
| 0006 | 22 | | GA | | 114-0 | 23-42-11 | D04522 | 1 | | | D41700P | 3 | | | 115-199 |
| 0007 | 22 | | GA | | 8-2 | 33-25-11 | L00519 | =P | Z2 | | SP00536 | | 9 | | 001-099 |
| 0007 | 22 | | GA | | 8-0 | 33-25-11 | L00519 | =P | Z2 | | SP00536 | | 9 | | 115-199 |
| 0008 | 22 | | GA | | 8-1 | 33-25-11 | L00520 | =P | Z2 | | SP00534 | | 9 | | 001-099 |
| 0008 | 22 | | GA | | 8-0 | 33-25-11 | L00520 | =P | Z2 | | SP00534 | | 9 | | 115-199 |
| 0009 | 20 | | GA | | 1-4 | 33-25-11 | SM00009 | | 9 | | GD01446 | DC.. | E | | 001-099 |
| 0009 | 20 | | GA | | 3-0 | 33-25-11 | SM00009 | | 9 | | GD01446 | DC.. | E | | 115-199 |
| 0010 | 22 | | GA | | 36-4 | 23-42-11 | L00324 | =P | Z2 | | D41700P | 4 | | | 001-099 |
| 0010 | 22 | | GA | | 36-0 | 23-42-11 | L00324 | =P | Z2 | | D41700P | 4 | | | 115-199 |
| 0013 | 24 | | GK | | 85-6 | 38-32-11 | D40494J | 1 | | | D00046 | 34 | | | 001-099 |
| 0013 | 18 | | GA | | 86-0 | 38-32-11 | D40494J | 1 | | | D00046 | 34 | | | 115-199 |
| 0014 | 24 | | GK | | 85-6 | 38-32-11 | D40494J | 2 | | | D00046 | 35 | | | 001-099 |
| 0014 | 18 | | GA | | 86-0 | 38-32-11 | D40494J | 2 | | | D00046 | 35 | | | 115-199 |
| 0015 | 24 | | GK | | 85-6 | 38-32-11 | D40494J | 3 | | | D00046 | 36 | | | 001-099 |
| 0015 | 18 | | GA | | 86-0 | 38-32-11 | D40494J | 3 | | | D00046 | 36 | | | 115-199 |
| 0016 | 24 | | GK | | 81-0 | 38-32-11 | D40494J | 4 | | | D00048 | 34 | | | 001-099 |
| 0016 | 18 | | GA | | 81-0 | 38-32-11 | D40494J | 4 | | | D00048 | 34 | | | 115-199 |
| 0017 | 24 | | GK | | 81-0 | 38-32-11 | D40494J | 5 | | | D00048 | 35 | | | 001-099 |
| 0017 | 18 | | GA | | 81-0 | 38-32-11 | D40494J | 5 | | | D00048 | 35 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3670

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3672 | 286N3672 | | | MISC. LIGHTING ,RIGHT (continued) | | | | | | | | | | | |
| 0018 | 24 | | GK | | 81-0 | 38-32-11 | D40494J | | 6 | | D00048 | | 36 | | 001-099 |
| 0018 | 18 | | GA | | 81-0 | 38-32-11 | D40494J | | 6 | | D00048 | | 36 | | 115-199 |
| 0019 | 20 | | GA | | 91-10 | 38-13-11 | D41302P | | 21 | | D00048 | | 38 | | 001-099 |
| 0019 | 18 | | GA | | 92-0 | 38-13-11 | D41302P | | 21 | | D00048 | | 38 | | 115-199 |
| 0020 | 20 | | GA | | 96-4 | 38-13-11 | D41302P | | 23 | | D00046 | | 38 | | 001-099 |
| 0020 | 18 | | GA | | 97-0 | 38-13-11 | D41302P | | 23 | | D00046 | | 38 | | 115-199 |
| 0021 | 22 | | GA | | 37-8 | 23-42-11 | D41700P | | 2 | | D04518 | | 1 | | 001-099 |
| 0021 | 22 | | GA | | 37-0 | 23-42-11 | D41700P | | 2 | | D04518 | | 2 | | 115-199 |
| 0022 | 22 | | GA | | 5-3 | 33-25-11 | SP01248 | | | 9 | D04518 | | 6 | | 001-099 |
| 0022 | 22 | | GA | | 56-0 | 33-25-11 | SM00015 | | | 9 | D04518 | | 3 | | 115-199 |
| 0023 | 22 | | GA | | 5-3 | 33-25-11 | SP01248 | | | 9 | D04518 | | 8 | | 001-099 |
| 0023 | 22 | | GA | | 35-0 | 33-25-11 | SP00536 | | | 9 | D04518 | | 1 | | 115-199 |
| 0024 | 22 | | GA | | 5-3 | 33-25-11 | SP00538 | | | 9 | D04518 | | 7 | | 001-099 |
| 0025 | 22 | | GA | | 88-11 | 38-32-21 | D41302P | | 16 | | SM00001 | | | 9 | 001-099 |
| 0025 | 20 | | GA | | 89-0 | 38-32-21 | D41302P | | 16 | | SM00001 | | | 9 | 115-199 |
| 0026 | 24 | | GK | | 88-11 | 38-32-21 | D41302P | | 19 | | SM00002 | | | 9 | 001-099 |
| 0026 | 20 | | GA | | 89-0 | 38-32-21 | D41302P | | 19 | | SM00002 | | | 9 | 115-199 |
| 0027 | 16 | | GA | | 88-11 | 33-26-11 | D41302P | | 5 | 16 | SM00003 | | | 9 | 001-099 |
| 0027 | 22 | | GA | | 89-0 | 33-26-11 | D41302P | | 5 | | SM00003 | | | 9 | 115-199 |
| 0028 | 22 | | GA | | 88-11 | 33-26-11 | D41302P | | 3 | | SM00004 | | | 9 | 001-099 |
| 0028 | 22 | | GA | | 89-0 | 33-26-11 | D41302P | | 3 | | SM00004 | | | 9 | 115-199 |
| 0029 | 22 | | GA | | 88-11 | 33-26-11 | D41302P | | 4 | | SM00005 | | | 9 | 001-099 |
| 0029 | 22 | | GA | | 89-0 | 33-26-11 | D41302P | | 4 | | SM00005 | | | 9 | 115-199 |
| 0030 | 20 | | GA | | 88-11 | 33-24-11 | D41302P | | 14 | | SM00006 | | | 9 | 001-099 |
| 0030 | 18 | | GA | | 89-0 | 33-24-11 | D41302P | | 14 | 18 | SM00006 | | | 9 | 115-199 |
| 0031 | 18 | | GA | | 89-0 | 33-24-11 | D41302P | | 15 | 18 | SM00007 | | | 9 | 115-199 |
| 0032 | 22 | | GA | | 88-11 | 33-26-31 | D41302P | | 6 | | SM00008 | | | 9 | 001-099 |
| 0032 | 22 | | GA | | 89-0 | 33-26-31 | D41302P | | 6 | | SM00008 | | | 9 | 115-199 |
| 0033 | 22 | | GA | | 32-7 | 33-25-11 | D04518 | | 3 | | SP00540 | | | 9 | 001-099 |
| 0034 | 22 | | GA | | 5-3 | 33-25-11 | D04518 | | 2 | | SP00542 | | | 9 | 001-099 |
| 0036 | 22 | | GA | | 8-5 | 38-32-21 | SM00001 | | | 9 | D00046 | | 19 | | 001-099 |
| 0036 | 20 | | GA | | 9-0 | 38-32-21 | SM00001 | | | 9 | D00046 | | 19 | | 115-199 |
| 0037 | 24 | | GK | | 8-5 | 38-32-21 | SM00002 | | | 9 | D00046 | | 20 | | 001-099 |
| 0037 | 20 | | GA | | 9-0 | 38-32-21 | SM00002 | | | 9 | D00046 | | 20 | | 115-199 |
| 0038 | 16 | | GA | | 8-5 | 33-26-11 | SM00003 | | | 9 | D00046 | | 18 | 16 | 001-099 |
| 0038 | 22 | | GA | | 9-0 | 33-26-11 | SM00003 | | | 9 | D00046 | | 18 | | 115-199 |
| 0039 | 22 | | GA | | 8-5 | 33-26-11 | SM00004 | | | 9 | D00046 | | 16 | | 001-099 |
| 0039 | 22 | | GA | | 9-0 | 33-26-11 | SM00004 | | | 9 | D00046 | | 16 | | 115-199 |
| 0040 | 22 | | GA | | 8-5 | 33-26-11 | SM00005 | | | 9 | D00046 | | 6 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3670

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|-----------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3672 | 286N3672 | | | | MISC. LIGHTING ,RIGHT (continued) | | | | | | | | | | | |
| 0040 | 22 | | GA | | 9-0 | 33-26-11 | SM00005 | | | 9 | | D00046 | 6 | | | 115-199 |
| 0041 | 20 | | GA | | 8-5 | 33-24-11 | SM00006 | | | 9 | | D00046 | 7 | | | 001-099 |
| 0041 | 18 | | GA | | 9-0 | 33-24-11 | SM00006 | | | 9 | | D00046 | 7 | 18 | | 115-199 |
| 0042 | 20 | | GA | | 3-11 | 33-24-11 | GD02888 | AC.. | E | | | D00046 | 8 | | | 001-099 |
| 0042 | 18 | | GA | | 9-0 | 33-24-11 | SM00007 | | | 9 | | D00046 | 8 | 18 | | 115-199 |
| 0043 | 22 | | GA | | 8-5 | 33-26-31 | SM00008 | | | 9 | | L00354 | =P | C | | 001-099 |
| 0043 | 22 | | GA | | 11-0 | 33-26-31 | SM00008 | | | 9 | | L00354 | =P | C | | 115-199 |
| 0044 | 22 | | GA | | 3-6 | 33-26-11 | D00048 | | 6 | | | SM00005 | | 9 | | 001-099 |
| 0044 | 22 | | GA | | 4-0 | 33-26-11 | D00048 | | 6 | | | SM00005 | | 9 | | 115-199 |
| 0045 | 20 | | GA | | 3-6 | 33-24-11 | D00048 | | 7 | | | SM00006 | | 9 | | 001-099 |
| 0045 | 18 | | GA | | 4-0 | 33-24-11 | D00048 | | 7 | 18 | | SM00006 | | 9 | | 115-199 |
| 0046 | 22 | | GA | | 6-10 | 33-25-14 | D00046 | | 5 | | | D03462 | 5 | | | 001-099 |
| 0046 | 22 | | GA | | 7-0 | 33-25-14 | D00046 | | 5 | | | D03462 | 5 | | | 115-199 |
| 0047 | 22 | | GA | | 6-10 | 33-25-14 | D00046 | | 2 | | | D03462 | 2 | | | 001-099 |
| 0047 | 22 | | GA | | 7-0 | 33-25-14 | D00046 | | 2 | | | D03462 | 2 | | | 115-199 |
| 0048 | 18 | | GA | | 6-10 | 35-21-13 | D00046 | | 15 | | | D03462 | 10 | | | 001-099 |
| 0048 | 18 | | GA | | 7-0 | 35-21-13 | D00046 | | 15 | | | D03462 | 10 | | | 115-199 |
| 0050 | 16 | | GA | | 2-10 | 38-32-11 | D00046 | | 37 | | | GD01453 | AC.. | E | | 001-099 |
| 0050 | 16 | | GA | | 3-0 | 38-32-11 | D00046 | | 37 | | | GD01453 | AC.. | E | | 115-199 |
| 0053 | 20 | | GA | | 3-4 | 38-32-21 | D00046 | | 22 | | | GD01451 | DC.. | E | | 001-099 |
| 0053 | 18 | | GA | | 12-0 | 38-32-21 | D00046 | | 22 | | | GD01451 | DC.. | E | | 115-199 |
| 0054 | 22 | | GA | | 3-6 | 38-32-21 | D00048 | | 19 | | | SM00001 | | 9 | | 001-099 |
| 0054 | 20 | | GA | | 4-0 | 38-32-21 | D00048 | | 19 | | | SM00001 | | 9 | | 115-199 |
| 0055 | 24 | | GK | | 3-6 | 38-32-21 | D00048 | | 20 | | | SM00002 | | 9 | | 001-099 |
| 0055 | 20 | | GA | | 4-0 | 38-32-21 | D00048 | | 20 | | | SM00002 | | 9 | | 115-199 |
| 0056 | 16 | | GA | | 3-6 | 33-26-11 | D00048 | | 18 | 16 | | SM00003 | | 9 | | 001-099 |
| 0056 | 22 | | GA | | 4-0 | 33-26-11 | D00048 | | 18 | | | SM00003 | | 9 | | 115-199 |
| 0057 | 22 | | GA | | 3-6 | 33-26-11 | D00048 | | 16 | | | SM00004 | | 9 | | 001-099 |
| 0057 | 22 | | GA | | 4-0 | 33-26-11 | D00048 | | 16 | | | SM00004 | | 9 | | 115-199 |
| 0058 | 20 | | GA | | 4-7 | 33-24-11 | D00048 | | 8 | | | GD02890 | AC.. | E | | 001-099 |
| 0058 | 18 | | GA | | 4-0 | 33-24-11 | D00048 | | 8 | 18 | | SM00007 | | 9 | | 115-199 |
| 0059 | 22 | | GA | | 7-0 | 33-25-24 | D00048 | | 2 | | | D03468 | 2 | | | 001-099 |
| 0059 | 22 | | GA | | 7-0 | 33-25-24 | D03468 | | 2 | | | D00048 | 2 | | | 115-199 |
| 0060 | 22 | | GA | | 7-0 | 33-25-24 | D00048 | | 5 | | | D03468 | 5 | | | 001-099 |
| 0060 | 22 | | GA | | 7-0 | 33-25-24 | D03468 | | 5 | | | D00048 | 5 | | | 115-199 |
| 0062 | 18 | | GA | | 7-0 | 35-21-22 | D03468 | | 10 | | | D00048 | 15 | | | ALL |
| 0063 | 22 | | GA | | 6-0 | 33-26-21 | L00641 | | 1 | C | * | L00616 | 1 | C | | 115-199 |
| 0064 | 16 | | GA | | 4-7 | 38-32-11 | GD01456 | AC.. | E | | | D00048 | 37 | | | 001-099 |
| 0064 | 16 | | GA | | 5-0 | 38-32-11 | GD01456 | AC.. | E | | | D00048 | 37 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3670

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | From | | | | To | | | | | |
|------------|-------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3672 | 286N3672 | | | MISC. LIGHTING ,RIGHT (continued) | | | | | | | | | | | |
| 0065 | 20 | | GA | | 8-0 | 33-26-21 | L00641 | 2 | C | | L00642 | 2 | C | * | 115-199 |
| 0066 | 20 | | GA | | 5-0 | 33-26-21 | L00642 | 2 | C | * | L00617 | 2 | C | * | 115-199 |
| 0067 | 20 | | GA | | 4-7 | 38-32-21 | GD01454 | DC.. | E | | D00048 | 22 | | | 001-099 |
| 0067 | 18 | | GA | | 5-0 | 38-32-21 | GD01454 | DC.. | E | | D00048 | 22 | | | 115-199 |
| 0069 | 22 | | GA | | 15-0 | 33-26-21 | L00419 | LAV | C | * | L00641 | 1 | C | * | 115-199 |
| 0070 | 22 | | GA | | 18-0 | 33-26-21 | L00419 | OCC | C | * | L00642 | 1 | C | * | 115-199 |
| 0071 | 16 | | GA | | 89-7 | 33-26-21 | L00419 | LAV | C | * | D41302P | 7 | 16 | | 001-099 |
| 0071 | 22 | | GA | | 89-0 | 33-26-21 | SM00016 | | 9 | | D41302P | 7 | | | 115-199 |
| 0072 | 22 | | GA | | 11-0 | 33-26-21 | L00419 | OCC | C | * | D00048 | 4 | | | 115-199 |
| 0073 | 16 | | GA | | 4-7 | 33-26-21 | L00419 | GND | C | | GD01461 | AC.. | E | | 001-099 |
| 0073 | 20 | | GA | | 5-0 | 33-26-21 | L00419 | GND | C | | GD01461 | AC.. | E | | 115-199 |
| 0074 | 16 | | GA | | 8-2 | 33-26-21 | D00048 | 3 | 16 | | D00046 | 4 | 16 | | 001-099 |
| 0074 | 22 | | GA | | 8-0 | 33-26-21 | D00046 | 4 | | | D00048 | 3 | | | 115-199 |
| 0075 | 16 | | GA | | 18-1 | 33-26-21 | D00046 | 3 | 16 | | SP00550 | | 9 | | 001-099 |
| 0075 | 22 | | GA | | 9-0 | 33-26-21 | D00046 | 3 | | | SM00016 | | 9 | | 115-199 |
| 0076 | 20 | | GA | | 2-2 | 33-26-31 | L00354 | =G | C | | GD01459 | AC.. | E | | 001-099 |
| 0076 | 20 | | GA | | 3-0 | 33-26-31 | L00354 | =G | C | | GD01459 | AC.. | E | | 115-199 |
| 0077 | 20 | | GA | | 4-2 | 33-26-31 | L00355 | =G | C | | GD01460 | AC.. | E | | 001-099 |
| 0077 | 20 | | GA | | 4-0 | 33-26-31 | L00355 | =G | C | | GD01460 | AC.. | E | | 115-199 |
| 0078 | 16 | | GA | | 12-1 | 33-26-21 | D00048 | 4 | 16 | | L00419 | OCC | C | * | 001-099 |
| 0078 | 20 | | GA | | 92-0 | 33-22-13 | D00048 | CAP | Y | | D41302P | 20 | | | 115-199 |
| 0082 | 24 | | GK | | 40-10 | 33-51-13 | SP00290 | | 9 | | D41302P | 9 | | | 001-099 |
| 0082 | 22 | | GA | | 41-0 | 33-51-13 | SP00290 | | 9 | | D41302P | 9 | | | 115-199 |
| 0083 | 24 | | GK | | 85-4 | 33-51-14 | D41302P | 11 | | | SP00286 | | 9 | | 001-099 |
| 0083 | 24 | | GK | | 91-0 | 33-51-14 | SP00286 | | 9 | | D41302P | 11 | | | 115-199 |
| 0084 | 22 | | GA | | 38-5 | 33-51-12 | SP01592 | | 9 | | D41302P | 10 | | | 001-099 |
| 0084 | 22 | | GA | | 38-0 | 33-51-12 | SP01592 | | 9 | | D41302P | 10 | | | 115-199 |
| 0085 | 24 | | GK | | 119-0 | 33-51-15 | SP00294 | | 9 | | D41302P | 13 | | | 001-099 |
| 0085 | 24 | | GK | | 121-0 | 33-51-15 | SP00294 | | 9 | | D41302P | 13 | | | 115-199 |
| 0086 | 22 | | GA | | 47-8 | 33-51-14 | SP01152 | | 9 | | SP01072 | | 9 | | 001-099 |
| 0086 | 22 | | GA | | 54-0 | 33-51-14 | SP01072 | | 9 | | SP01152 | | 9 | | 115-199 |
| 0087 | 22 | | GA | | 32-3 | 33-51-12 | SP01154 | | 9 | | SP01586 | | 9 | | 001-099 |
| 0087 | 22 | | GA | | 35-0 | 33-51-12 | SP01154 | | 9 | | SP01586 | | 9 | | 115-199 |
| 0088 | 22 | | GA | | 38-5 | 33-51-12 | SP01154 | | 9 | | D41302P | 12 | | | 001-099 |
| 0088 | 22 | | GA | | 38-0 | 33-51-12 | SP01154 | | 9 | | D41302P | 12 | | | 115-199 |
| 0089 | 24 | | GK | | 38-5 | 33-51-12 | SP01070 | | 9 | | D41302P | 8 | | | 001-099 |
| 0089 | 24 | | GK | | 38-0 | 33-51-12 | SP01070 | | 9 | | D41302P | 8 | | | 115-199 |
| 0090 | 22 | | GA | | 86-4 | 23-42-11 | SM00038 | | 9 | | D41700P | 6 | | | 001-099 |
| 0090 | 22 | | GA | | 89-0 | 23-42-11 | D07156 | 2 | | | D41700P | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3670

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | | |
|------------|-------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3672 | 286N3672 | | | MISC. LIGHTING ,RIGHT (continued) | | | | | | | | | | | | |
| 0091 | 22 | | GA | | 15-0 | 33-25-14 | D04520 | 2 | | | SP00544 | | 9 | | 001-099 | |
| 0092 | 22 | | GA | | 19-5 | 33-25-14 | D04520 | 3 | | | SP00546 | | 9 | | 001-099 | |
| 0093 | 20 | | GA | | 1-6 | 33-25-14 | D04520 | 4 | | | GD01463 | DC.. | E | | 001-099 | |
| 0093 | 20 | | GA | | 3-0 | 23-42-11 | D07156 | 4 | | | GD01451 | DC.. | E | | 115-199 | |
| 0094 | 22 | | GA | | 5-1 | 33-26-31 | L00355 | =P | C | | SM00008 | | 9 | | 001-099 | |
| 0094 | 22 | | GA | | 5-0 | 33-26-31 | L00355 | =P | C | | SM00008 | | 9 | | 115-199 | |
| 0095 | 22 | | GA | | 42-4 | 33-25-14 | D04522 | 3 | | | SP00546 | | 9 | | 001-099 | |
| 0095 | 22 | | GA | | 33-0 | 33-25-14 | D04522 | 10 | | | SM00015 | | 9 | | 115-199 | |
| 0096 | 22 | | GA | | 6-8 | 33-25-14 | D04522 | 2 | | | SP00548 | | 9 | | 001-099 | |
| 0096 | 22 | | GA | | 9-0 | 33-25-14 | D04522 | 3 | | | SP00548 | | 9 | | 115-199 | |
| 0097 | 20 | | GA | | 3-2 | 33-25-14 | D04522 | 4 | | | GD01464 | DC.. | E | | 001-099 | |
| 0097 | 20 | | GA | | 3-0 | 33-25-14 | D04522 | 4 | | | GD01464 | DC.. | E | | 115-199 | |
| 0098 | 22 | | GA | | 18-1 | 33-25-14 | SP00546 | | 9 | | D00046 | | 17 | | 001-099 | |
| 0098 | 22 | | GA | | 9-0 | 33-25-14 | SM00015 | | 9 | | D00046 | | 17 | | 115-199 | |
| 0099 | 22 | | GA | | 13-7 | 33-25-24 | SP00546 | | 9 | | D00048 | | 17 | | 001-099 | |
| 0099 | 22 | | GA | | 4-0 | 33-25-24 | SM00015 | | 9 | | D00048 | | 17 | | 115-199 | |
| 0100 | 20 | | GA | | 2-1 | 33-25-11 | D04518 | 9 | | | GD01450 | DC.. | E | | 001-099 | |
| 0100 | 20 | | GA | | 2-0 | 33-25-11 | D04518 | 4 | | | GD00502 | DC.. | E | | 115-199 | |
| 0101 | 16 | | GA | | 4-7 | 33-26-11 | GD01455 | ST.. | E | | D00048 | | 1 | | 001-099 | |
| 0101 | 16 | | GA | | 5-0 | 33-26-11 | GD01455 | ST.. | E | | D00048 | | 1 | | 115-199 | |
| 0102 | 18 | | GA | | 4-7 | 33-26-11 | GD02890 | AC.. | E | | D00048 | | 39 | | 001-099 | |
| 0102 | 18 | | GA | | 5-0 | 33-26-11 | GD02890 | AC.. | E | | D00048 | | 39 | | 115-199 | |
| 0103 | 18 | | GA | | 4-7 | 33-26-11 | GD01456 | AC.. | E | | D00048 | | 40 | | 001-099 | |
| 0103 | 18 | | GA | | 5-0 | 33-26-11 | GD01456 | AC.. | E | | D00048 | | 40 | | 115-199 | |
| 0104 | 16 | | GA | | 2-11 | 33-26-11 | GD01452 | ST.. | E | | D00046 | | 1 | | 001-099 | |
| 0104 | 16 | | GA | | 3-0 | 33-26-11 | GD01452 | ST.. | E | | D00046 | | 1 | | 115-199 | |
| 0105 | 18 | | GA | | 3-11 | 33-26-11 | GD02888 | AC.. | E | | D00046 | | 39 | | 001-099 | |
| 0105 | 18 | | GA | | 4-0 | 33-26-11 | GD02888 | AC.. | E | | D00046 | | 39 | | 115-199 | |
| 0106 | 18 | | GA | | 2-10 | 33-26-11 | GD01453 | AC.. | E | | D00046 | | 40 | | 001-099 | |
| 0106 | 18 | | GA | | 3-0 | 33-26-11 | GD01453 | AC.. | E | | D00046 | | 40 | | 115-199 | |
| 0107 | 16 | | GA | | 2-11 | 38-32-11 | D00046 | 30 | | | GD01452 | ST.. | E | | 001-099 | |
| 0107 | 16 | | GA | | 3-0 | 38-32-11 | D00046 | 30 | | | GD01452 | ST.. | E | | 115-199 | |
| 0108 | 16 | | GA | | 4-7 | 38-32-11 | D00048 | 30 | | | GD01455 | ST.. | E | | 001-099 | |
| 0108 | 16 | | GA | | 5-0 | 38-32-11 | D00048 | 30 | | | GD01455 | ST.. | E | | 115-199 | |
| 0109 | 20 | | GA | | 6-10 | 35-21-13 | D00046 | 11 | | | D03462 | | 11 | | 001-099 | |
| 0109 | 20 | | GA | | 7-0 | 35-21-13 | D00046 | 11 | | | D03462 | | 11 | | 115-199 | |
| 0110 | 20 | | GA | | 7-0 | 35-21-22 | D00048 | 11 | | | D03468 | | 11 | | ALL | |
| 0111 | 22 | | GA | | 5-0 | 33-26-21 | L00617 | 1 | C | | L00642 | | 1 | C | * | 115-199 |
| 0114 | 20 | | GA | | 91-10 | SPARE | D41302P | 29 | | | D00048 | | 31 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3670

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3672 | | 286N3672 | | | | MISC. LIGHTING ,RIGHT (continued) | | | | | | | | | |
| 0114 | 20 | GA | | | 92-0 | SPARE | D41302P | 29 | | | D00048 | 31 | | | 115-199 |
| 0115 | 20 | GA | | | 91-10 | SPARE | D41302P | 30 | | | D00048 | 32 | | | 001-099 |
| 0115 | 20 | GA | | | 92-0 | SPARE | D41302P | 30 | | | D00048 | 32 | | | 115-199 |
| 0116 | 20 | GA | | | 91-10 | SPARE | D41302P | 31 | | | D00048 | 33 | | | 001-099 |
| 0116 | 20 | GA | | | 92-0 | SPARE | D41302P | 31 | | | D00048 | 33 | | | 115-199 |
| 0117 | 20 | GA | | | 96-4 | SPARE | D41302P | 24 | | | D00046 | 24 | | | 001-099 |
| 0117 | 20 | GA | | | 97-0 | SPARE | D41302P | 24 | | | D00046 | 24 | | | 115-199 |
| 0118 | 20 | GA | | | 96-4 | SPARE | D41302P | 25 | | | D00046 | CAP | Y | | 001-099 |
| 0118 | 20 | GA | | | 97-0 | SPARE | D41302P | 25 | | | D00046 | 25 | | | 115-199 |
| 0119 | 20 | GA | | | 96-4 | SPARE | D41302P | 26 | | | D00046 | CAP | Y | | 001-099 |
| 0119 | 20 | GA | | | 97-0 | SPARE | D41302P | 26 | | | D00046 | 26 | | | 115-199 |
| 0120 | 20 | GA | | | 2-11 | 33-25-11 | SM00009 | | 9 | | L00519 | =G | H | | 001-099 |
| 0120 | 20 | GA | | | 4-0 | 33-25-11 | SM00009 | | 9 | | L00519 | =G | H | | 115-199 |
| 0121 | 20 | GA | | | 2-11 | 33-25-11 | SM00009 | | 9 | | L00520 | =G | H | | 001-099 |
| 0121 | 20 | GA | | | 4-0 | 33-25-11 | SM00009 | | 9 | | L00520 | =G | H | | 115-199 |
| 0122 | 20 | GA | | | 2-11 | 33-25-11 | SM00009 | | 9 | | L00324 | =G | H | | 001-099 |
| 0122 | 20 | GA | | | 4-0 | 33-25-11 | SM00009 | | 9 | | L00324 | =G | H | | 115-199 |
| 0123 | 20 | GA | | | 5-3 | 33-51-13 | SP00302 | | 9 | | D04518 | 4 | | | 001-099 |
| 0123 | 22 | GA | | | 7-0 | 33-51-13 | SP00302 | | 9 | | D04518 | 6 | | | 115-199 |
| 0124 | 20 | GA | | | 2-1 | 33-51-13 | GD00502 | DC.. | E | | D04518 | 5 | | | 001-099 |
| 0124 | 20 | GA | | | 2-0 | 33-51-13 | GD00502 | DC.. | E | | D04518 | 8 | | | 115-199 |
| 0125 | 20 | GA | | | 6-8 | 33-51-14 | D04520 | 6 | | | SP01908 | | 9 | | 001-099 |
| 0125 | 20 | GA | | | 10-0 | 33-51-14 | SP01370 | | 9 | | D07156 | 6 | | | 115-199 |
| 0127 | 20 | GA | | | 6-0 | 33-51-15 | SP00306 | | 9 | | D04522 | 6 | | | 001-099 |
| 0127 | 20 | GA | | | 7-0 | 33-51-15 | SP00306 | | 9 | | D04522 | 6 | | | 115-199 |
| 0128 | 22 | GA | | | 1-0 | 33-26-31 | SM00008 | | 9 | | SM00010 | | 9 | | 115-199 |
| 0129 | 22 | GA | | | 59-0 | 33-26-31 | L00521 | CAP | Y | | SM00010 | | 9 | | 115-199 |
| 0130 | 20 | GA | | | 3-0 | 33-26-31 | L00521 | CAP | Y | | GD01835 | AC.. | E | | 115-199 |
| 0131 | 22 | GA | | | 51-0 | 33-26-31 | L00522 | CAP | Y | | SM00010 | | 9 | | 115-199 |
| 0132 | 20 | GA | | | 4-0 | 33-26-31 | L00522 | CAP | Y | | GD01836 | AC.. | E | | 115-199 |
| 0133 | 22 | GA | | | 8-0 | 33-25-12 | D05106 | 4 | | | SP01122 | | 9 | | 115-199 |
| 0135 | 20 | GA | | | 9-0 | 33-25-12 | D05106 | 1 | | | GD02235 | DC.. | E | | 115-199 |
| 0137 | 22 | GA | | | 8-0 | 33-25-12 | D05106 | 2 | | | SP01124 | | 9 | | 115-199 |
| 0138 | 22 | GA | | | 8-0 | 33-25-12 | D05106 | 3 | | | SP00542 | | 9 | | 115-199 |
| 0139 | 22 | GA | | | 42-0 | 33-25-14 | D04522 | 2 | | | SP00544 | | 9 | | 115-199 |
| 0140 | 22 | GA | | | 14-0 | 33-25-14 | B00148 | HI | C | | SP01130 | | 9 | | 115-199 |
| 0141 | 22 | GA | | | 5-0 | 33-25-21 | D05206 | 4 | | | SP01122 | | 9 | | 115-199 |
| 0143 | 20 | GA | | | 5-0 | 33-25-21 | D05206 | 1 | | | GD02236 | DC.. | E | | 115-199 |
| 0144 | 22 | GA | | | 5-0 | 33-25-21 | D05206 | 2 | | | SP01124 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3670

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | |
|------------|-------------|----|----|-----------------------------------|-------|----------|---------|------|------|--------|-------|---------|-------------|------|--------|---------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice | |
| W3672 | 286N3672 | | | MISC. LIGHTING ,RIGHT (continued) | | | | | | | | | | | | |
| 0147 | 22 | | GA | | 5-0 | 33-25-21 | D05206 | | 3 | | | SP00542 | | 9 | | 115-199 |
| 0148 | 22 | | GA | | 34-0 | 33-25-21 | B00144 | HI | C | | | SP01120 | | 9 | | 115-199 |
| 0149 | 22 | | GA | | 3-0 | 33-25-12 | TB0208A | A01 | 2 | | | SP01126 | | 9 | | 115-199 |
| 0150 | 22 | | GA | | 3-0 | 33-25-12 | TB0208A | A02 | 2 | | | SP01128 | | 9 | | 115-199 |
| 0151 | 22 | | GA | | 5-0 | 33-25-12 | TB0208A | C01 | 2 | | | D05098 | 1 | | | 115-199 |
| 0152 | 22 | | GA | | 5-0 | 33-25-12 | TB0208A | C02 | 2 | | | D05098 | 2 | | | 115-199 |
| 0153 | 22 | | GA | | 33-0 | 23-42-12 | D41700P | | 9 | | | B00144 | 28V | C | | 115-199 |
| 0154 | 20 | | GA | | 3-0 | 23-42-12 | GD02237 | DC.. | E | | | B00144 | GND | C | | 115-199 |
| 0155 | 24 | | GK | | 33-0 | 23-42-12 | D41700P | | 5 | | | B00144 | H/L | C | | 115-199 |
| 0156 | 22 | | GA | | 58-0 | 23-42-12 | D05098 | | 3 | | | SM00013 | | 9 | | 115-199 |
| 0157 | 20 | | GA | | 5-0 | 23-42-12 | D05098 | | 4 | | | GD00502 | DC.. | E | | 115-199 |
| 0158 | 16 | | GA | | 16-2 | 33-26-21 | L00419 | OCC | C | * | | L00420 | OCC | C | | 001-099 |
| 0158 | 24 | | GK | | 58-0 | 23-42-12 | D05098 | | 5 | | | SM00014 | | 9 | | 115-199 |
| 0159 | 16 | | GA | | 16-2 | 33-26-21 | L00419 | LAV | C | * | | L00420 | LAV | C | | 001-099 |
| 0159 | 22 | | GA | | 38-0 | 23-42-12 | B00148 | 28V | C | | | SM00013 | | 9 | | 115-199 |
| 0160 | 16 | | GA | | 7-4 | 33-26-21 | L00420 | GND | C | | | GD01462 | AC.. | E | | 001-099 |
| 0160 | 20 | | GA | | 5-0 | 23-42-12 | B00148 | GND | C | | | GD02239 | DC.. | E | | 115-199 |
| 0161 | 24 | | GK | | 119-0 | 23-42-12 | B00148 | H/L | C | | | D41700P | 7 | | | 115-199 |
| 0162 | 22 | | GA | | 83-0 | 23-42-12 | D41700P | | 8 | | | SM00013 | | 9 | | 115-199 |
| 0163 | 22 | | GA | | 83-0 | 23-42-12 | D41700P | | 6 | | | SM00014 | | 9 | | 115-199 |
| 0164 | 22 | | GA | | 8-0 | 23-42-12 | B00145 | 28V | C | | | SM00013 | | 9 | | 115-199 |
| 0165 | 20 | | GA | | 4-0 | 23-42-12 | B00145 | GND | C | | | GD02420 | DC.. | E | | 115-199 |
| 0166 | 24 | | GK | | 8-0 | 23-42-12 | B00145 | H/L | C | | | SM00014 | | 9 | | 115-199 |
| 0167 | 22 | | GA | | 17-0 | 33-25-24 | B00145 | HI | C | | | SP01594 | | 9 | | 115-199 |
| 0168 | 22 | | GA | | 32-3 | 33-51-12 | SP01072 | | 9 | | | SP01592 | | 9 | | 001-099 |
| 0168 | 22 | | GA | | 33-0 | 33-51-12 | SP01072 | | 9 | | | SP01592 | | 9 | | 115-199 |
| 0169 | 22 | | GA | | 47-8 | 33-51-14 | SP01586 | | 9 | | | SP01588 | | 9 | | 001-099 |
| 0169 | 22 | | GA | | 55-0 | 33-51-14 | SP01586 | | 9 | | | SP01588 | | 9 | | 115-199 |
| 0172 | 20 | | GA | | 1-6 | 33-51-14 | D04520 | | 8 | | | GD00483 | DC.. | E | | 001-099 |
| 0172 | 20 | | GA | | 3-0 | 33-51-14 | D07156 | | 8 | | | GD03264 | DC.. | E | | 115-199 |
| 0173 | 20 | | GA | | 3-2 | 33-51-15 | D04522 | | 8 | | | GD00490 | DC.. | E | | 001-099 |
| 0173 | 20 | | GA | | 3-0 | 33-51-15 | D04522 | | 8 | | | GD00490 | DC.. | E | | 115-199 |
| 0175 | 20 | | GA | | 85-6 | SPARE | D40494J | | 8 | | | D00046 | 10 | | | 001-099 |
| 0175 | 18 | | GA | | 5-0 | 35-21-12 | D05098 | | 8 | 18 | | SP01164 | | 9 | | 115-199 |
| 0176 | 20 | | GA | | 5-0 | 35-21-12 | D05098 | | 9 | | | SP01166 | | 9 | | 115-199 |
| 0177 | 20 | | GA | | 10-0 | 33-22-12 | D05098 | | 6 | | | SP01162 | | 9 | | 115-199 |
| 0178 | 22 | | GA | | 5-0 | 33-22-12 | D05098 | | 7 | | | SP01160 | | 9 | | 115-199 |
| 0179 | 22 | | GA | | 9-0 | 33-26-21 | SM00016 | | 9 | | | L00419 | LAV | C | * | 115-199 |
| 0180 | 20 | | GA | | 4-0 | 33-26-21 | L00616 | | 2 | C | * | L00617 | 2 | C | * | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3670

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3672 | 286N3672 | | | MISC. LIGHTING ,RIGHT (continued) | | | | | | | | | | | |
| 0181 | 22 | | GA | | 5-0 | 33-25-12 | D05298 | | | | TB0208A | C01 | 2 | | 115-199 |
| 0182 | 24 | | GK | | 83-5 | SPARE | SP01266 | | 9 | | D00048 | 24 | | | 001-099 |
| 0182 | 22 | | GA | | 5-0 | 33-25-12 | D05298 | | 2 | | TB0208A | C02 | 2 | | 115-199 |
| 0183 | 22 | | GA | | 58-0 | 23-42-12 | D05298 | | 3 | | SM00013 | | 9 | | 115-199 |
| 0184 | 20 | | GA | | 2-0 | 23-42-12 | D05298 | | 4 | | GD03102 | DC.. | E | | 115-199 |
| 0185 | 24 | | GK | | 58-0 | 23-42-12 | D05298 | | 5 | | SM00014 | | 9 | | 115-199 |
| 0196 | 20 | | GA | | 14-0 | 33-26-21 | L00616 | | 2 | C | GD02888 | AC.. | E | | 115-199 |
| 0245 | 22 | | GA | | 6-4 | 23-42-11 | SM00038 | | 9 | | D04520 | 1 | | | 001-099 |
| 0246 | 22 | | GA | | 7-2 | SPARE | D07156 | | 1 | | SM00038 | | 9 | | 001-099 |
| 0247 | 22 | | GA | | 12-2 | SPARE | D07156 | | 2 | | SP00544 | | 9 | | 001-099 |
| 0248 | 22 | | GA | | 16-7 | SPARE | D07156 | | 3 | | SP00546 | | 9 | | 001-099 |
| 0249 | 20 | | GA | | 4-5 | SPARE | D07156 | | 4 | | GD01451 | DC.. | E | | 001-099 |
| 0250 | 20 | | GA | | 9-2 | SPARE | D07156 | | 6 | | SP01908 | | 9 | | 001-099 |
| 0251 | 20 | | GA | | 2-7 | SPARE | D07156 | | 8 | | GD03264 | DC.. | E | | 001-099 |
| 2001B | 22 | | GB | AA | 6-10 | 23-31-22 | D00046 | | 13 | | D03462 | 14 | | | 001-099 |
| 2001B | 22 | | GB | AA | 7-0 | 23-31-22 | D00046 | | 13 | | D03462 | 13 | | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 23-31-22 | D00046 | | 14 | | D03462 | 13 | | | 001-099 |
| 2001R | 22 | | GB | AA | 0-0 | 23-31-22 | D00046 | | 14 | | D03462 | 14 | | | 115-199 |
| 2002B | 22 | | GB | AB | 7-0 | 23-31-32 | D03468 | | 14 | | D00048 | 13 | | | 001-099 |
| 2002B | 22 | | GB | AB | 7-0 | 23-31-32 | D00048 | | 13 | | D03468 | 13 | | | 115-199 |
| 2002R | 22 | | GB | AB | 0-0 | 23-31-32 | D03468 | | 13 | | D00048 | 14 | | | 001-099 |
| 2002R | 22 | | GB | AB | 0-0 | 23-31-32 | D00048 | | 14 | | D03468 | 14 | | | 115-199 |
| 2004B | 24 | | GL | AD | 8-2 | SPARE | D00048 | | 25 | | D00046 | 25 | | | 001-099 |
| 2004R | 24 | | GL | AD | 0-0 | SPARE | D00048 | | 26 | | D00046 | 26 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3670

Page 8 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------|-------------|----|-------|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3682 | 286N3682 | | | | E3-4 TO RIGHT ENTRY DOORS PROXIMITY SWITCHES | | | | | | | | | | | |
| 0001 | 20 | GA | | | 33-0 | 25-66-11 | D41708P | 1 | | | | SM00001 | 9 | | | ALL |
| 0002 | 20 | GA | | | 23-0 | 25-66-11 | L00404 | C | B | | | SM00001 | 9 | | | 001-099 |
| 0002 | 20 | GA | | | 24-0 | 25-66-11 | L00404 | C | B | | | SM00001 | 9 | | | 115-199 |
| 0003 | 20 | GA | | | 28-0 | 25-66-11 | L00404 | 2 | B | * | | SP00068 | 9 | | | 001-099 |
| 0003 | 20 | GA | | | 29-0 | 25-66-11 | L00404 | 2 | B | | | SP00068 | 9 | | | 115-199 |
| 0004 | 20 | GA | | | 17-0 | 25-66-11 | SM00001 | 9 | | | | SM00002 | 9 | | | 001-099 |
| 0004 | 20 | GA | | | 16-0 | 25-66-11 | SM00001 | 9 | | | | SM00002 | 9 | | | 115-199 |
| 0005 | 20 | GA | | | 7-0 | 25-66-11 | SM00002 | 9 | | | | L00406 | C | B | | 001-099 |
| 0005 | 20 | GA | | | 6-0 | 25-66-11 | SM00002 | 9 | | | | L00406 | C | B | | 115-199 |
| 0006 | 20 | GA | | | 23-0 | 25-66-11 | L00406 | 2 | B | * | | SP00074 | 9 | | | 001-099 |
| 0006 | 20 | GA | | | 24-0 | 25-66-11 | L00406 | 2 | B | | | SP00074 | 9 | | | 115-199 |
| 0007 | 20 | GA | | | 86-0 | 25-66-11 | SM00002 | 9 | | | | L00408 | C | B | | 001-099 |
| 0007 | 20 | GA | | | 87-0 | 25-66-11 | SM00002 | 9 | | | | L00408 | C | B | | 115-199 |
| 0008 | 20 | GA | | | 26-0 | 25-66-11 | L00408 | 2 | B | * | | SP00078 | 9 | | | 001-099 |
| 0008 | 20 | GA | | | 26-0 | 25-66-11 | L00408 | 2 | B | | | SP00078 | 9 | | | 115-199 |
| 0009 | 20 | GA | | | 2-0 | 25-66-11 | L00404 | 2 | B | * | | L00404 | 1 | B | | 001-099 |
| 0009 | 20 | GA | | | 29-0 | 25-66-11 | SP00068 | 9 | | | | L00404 | 1 | B | | 115-199 |
| 0010 | 20 | GA | | | 3-0 | 25-66-11 | L00406 | 2 | B | * | | L00406 | 1 | B | | 001-099 |
| 0010 | 20 | GA | | | 24-0 | 25-66-11 | SP00074 | 9 | | | | L00406 | 1 | B | | 115-199 |
| 0011 | 20 | GA | | | 2-0 | 25-66-11 | L00408 | 2 | B | * | | L00408 | 1 | B | | 001-099 |
| 0011 | 20 | GA | | | 26-0 | 25-66-11 | SP00078 | 9 | | | | L00408 | 1 | B | | 115-199 |
| 0012 | 20 | GA | | | 37-0 | 25-66-11 | SP00070 | 9 | | | | SP01478 | 9 | | | ALL |
| 0013 | 20 | GA | | | 32-0 | 25-66-11 | SP00076 | 9 | | | | SP01484 | 9 | | | 001-099 |
| 0013 | 20 | GA | | | 33-0 | 25-66-11 | SP00076 | 9 | | | | SP01484 | 9 | | | 115-199 |
| 0014 | 20 | GA | | | 41-0 | 25-66-11 | SP00080 | 9 | | | | SP01554 | 9 | | | 001-099 |
| 0014 | 20 | GA | | | 50-0 | 25-66-11 | SP00080 | 9 | | | | SP01554 | 9 | | | 115-199 |
| 0015 | 20 | GA | | | 9-0 | 25-66-11 | GD02922 | AC.. | E | | | SP00726 | 9 | | | 001-099 |
| 0015 | 20 | GA | | | 11-0 | 25-66-11 | GD00034 | AC.. | E | | | SP00726 | 9 | | | 115-199 |
| 0016 | 20 | GA | | | 5-0 | 25-66-11 | GD02924 | AC.. | E | | | SP00728 | 9 | | | 001-099 |
| 0016 | 20 | GA | | | 12-0 | 25-66-11 | GD00036 | AC.. | E | | | SP00728 | 9 | | | 115-199 |
| 0017 | 20 | GA | | | 13-0 | 25-66-11 | GD02926 | AC.. | E | | | SP00730 | 9 | | | 001-099 |
| 0017 | 20 | GA | | | 16-0 | 25-66-11 | GD00038 | AC.. | E | | | SP00730 | 9 | | | 115-199 |
| 2001B | 24 | GL | AA | | 62-0 | 52-71-21 | D41708P | 3 | | | | SP00156 | 9 | | | 001-099 |
| 2001B | 20 | GB | AA | | 62-0 | 52-71-21 | D41708P | 3 | | | | SP00156 | 9 | | | 115-199 |
| 2001R | 24 | GL | AA | | 0-0 | 52-71-21 | D41708P | 2 | | | | SP00154 | 9 | | | 001-099 |
| 2001R | 20 | GB | AA | | 0-0 | 52-71-21 | D41708P | 2 | | | | SP00154 | 9 | | | 115-199 |
| 2002B | 24 | GL | AB | | 58-0 | 52-71-21 | D41708P | 5 | | | | SP00160 | 9 | | | 001-099 |
| 2002B | 20 | GB | AB | | 59-0 | 52-71-21 | D41708P | 5 | | | | SP00160 | 9 | | | 115-199 |
| 2002R | 24 | GL | AB | | 0-0 | 52-71-21 | D41708P | 4 | | | | SP00158 | 9 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3680

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3682 | 286N3682 | | | E3-4 TO RIGHT ENTRY DOORS PROXIMITY SWITCHES (continued) | | | | | | | | | | | |
| 2002R | 20 | GB | AB | | 0-0 | 52-71-21 | D41708P | | | 4 | SP00158 | | | 9 | 115-199 |
| 2003B | 24 | GL | AC | | 110-0 | 52-71-21 | D41708P | | | 7 | SP00164 | | | 9 | 001-099 |
| 2003B | 20 | GB | AC | | 110-0 | 52-71-21 | D41708P | | | 7 | SP00164 | | | 9 | 115-199 |
| 2003R | 24 | GL | AC | | 0-0 | 52-71-21 | D41708P | | | 6 | SP00162 | | | 9 | 001-099 |
| 2003R | 20 | GB | AC | | 0-0 | 52-71-21 | D41708P | | | 6 | SP00162 | | | 9 | 115-199 |
| 2004B | 24 | GL | AD | | 144-0 | 52-71-21 | D41708P | | | 9 | SP00168 | | | 9 | 001-099 |
| 2004B | 20 | GB | AD | | 145-0 | 52-71-21 | D41708P | | | 9 | SP00168 | | | 9 | 115-199 |
| 2004R | 24 | GL | AD | | 0-0 | 52-71-21 | D41708P | | | 8 | SP00166 | | | 9 | 001-099 |
| 2004R | 20 | GB | AD | | 0-0 | 52-71-21 | D41708P | | | 8 | SP00166 | | | 9 | 115-199 |
| A-GA | | | | | 0-0 | 25-66-11 | S10216 | | BLU | | SP01478 | | | 9 | ALL |
| A-PA | | | | | 0-0 | 25-66-11 | S10216 | | RED | | SP00068 | | | 9 | ALL |
| B-GA | | | | | 0-0 | 25-66-11 | S10217 | | BLU | | SP00726 | | | 9 | ALL |
| B-PA | | | | | 0-0 | 25-66-11 | S10217 | | RED | | SP00070 | | | 9 | ALL |
| C-GA | | | | | 0-0 | 25-66-11 | S10220 | | BLU | | SP01484 | | | 9 | ALL |
| C-PA | | | | | 0-0 | 25-66-11 | S10220 | | RED | | SP00074 | | | 9 | ALL |
| D-GA | | | | | 0-0 | 25-66-11 | S10221 | | BLU | | SP00728 | | | 9 | ALL |
| D-PA | | | | | 0-0 | 25-66-11 | S10221 | | RED | | SP00076 | | | 9 | ALL |
| E-GA | | | | | 0-0 | 25-66-11 | S10224 | | BLU | | SP01554 | | | 9 | ALL |
| E-PA | | | | | 0-0 | 25-66-11 | S10224 | | RED | | SP00078 | | | 9 | ALL |
| F-GA | | | | | 0-0 | 25-66-11 | S10225 | | BLU | | SP00730 | | | 9 | ALL |
| F-PA | | | | | 0-0 | 25-66-11 | S10225 | | RED | | SP00080 | | | 9 | ALL |
| G-GA | | | | | 0-0 | 52-71-21 | S10090 | | BLU | | SP00156 | | | 9 | ALL |
| G-PA | | | | | 0-0 | 52-71-21 | S10090 | | RED | | SP00154 | | | 9 | ALL |
| H-GA | | | | | 0-0 | 52-71-21 | S10091 | | BLU | | SP00160 | | | 9 | ALL |
| H-PA | | | | | 0-0 | 52-71-21 | S10091 | | RED | | SP00158 | | | 9 | ALL |
| J-GA | | | | | 0-0 | 52-71-21 | S10092 | | BLU | | SP00164 | | | 9 | ALL |
| J-PA | | | | | 0-0 | 52-71-21 | S10092 | | RED | | SP00162 | | | 9 | ALL |
| K-GA | | | | | 0-0 | 52-71-21 | S10093 | | BLU | | SP00168 | | | 9 | ALL |
| K-PA | | | | | 0-0 | 52-71-21 | S10093 | | RED | | SP00166 | | | 9 | ALL |

WIRE LIST

D280N032

91-21-11

Section W3680

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-----|--------------------------------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W3692 | 286N3692 | | | | NSFSB-RIGHT,MID/FWD (STA 673) | | | | | | | | | | |
| 0001 | 20 | | GA | | 6-0 | 33-24-21 | D05292 | | 1 | | L00546 | 3 | C | | 115-199 |
| 0007 | 20 | | GA | | 6-0 | 33-24-21 | D05292 | | 7 | | L00546 | 1 | C | | 115-199 |
| 0008 | 16 | | GA | | 6-0 | 33-24-21 | D05292 | | 8 | | L00546 | 2 | C | | 115-199 |
| W3696 | 286N3696 | | | | NSFSB-RIGHT, MID/AFT (STA 737) | | | | | | | | | | |
| 0001 | 20 | | GA | | 4-0 | 33-24-21 | D05030 | | 1 | | L00532 | 3 | C | | 115-199 |
| 0007 | 20 | | GA | | 4-0 | 33-24-21 | D05030 | | 7 | | L00532 | 1 | C | | 115-199 |
| 0008 | 16 | | GA | | 4-0 | 33-24-21 | D05030 | | 8 | | L00532 | 2 | C | | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W3690
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD | | | | | | | | | |
| 0011G | 16 | GA | | | 10-11 | 33-24-12 | D05902 | | | | SM00011 | | | 9 | 001-099 |
| 0011G | 16 | GA | | | 10-7 | 33-24-12 | D05902 | | | | SM00011 | | | 9 | 115-199 |
| 0012WV | 22 | GA | | | 10-11 | 33-25-11 | D05902 | | | | SM00012 | | | 9 | 001-099 |
| 0012WV | 22 | GA | | | 10-7 | 33-25-11 | D05902 | | | | SM00012 | | | 9 | 115-199 |
| 0013WG | 22 | GA | | | 10-11 | 33-25-11 | D05902 | | | | SM00013 | | | 9 | 001-099 |
| 0013WG | 22 | GA | | | 10-7 | 33-25-11 | D05902 | | | | SM00013 | | | 9 | 115-199 |
| 0014WO | 22 | GA | | | 10-11 | 33-25-11 | D05902 | | | | SM00014 | | | 9 | 001-099 |
| 0014WO | 22 | GA | | | 10-7 | 33-25-11 | D05902 | | | | SM00014 | | | 9 | 115-199 |
| 0015V | 22 | GA | | | 10-11 | 33-25-11 | D05902 | | | | SM00015 | | | 9 | 001-099 |
| 0015V | 22 | GA | | | 10-7 | 33-25-11 | D05902 | | | | SM00015 | | | 9 | 115-199 |
| 0016WN | 16 | GA | | | 10-11 | 33-23-11 | D05902 | | | | SM00016 | | | 9 | 001-099 |
| 0016WN | 16 | GA | | | 10-7 | 33-23-11 | D05902 | | | | SM00016 | | | 9 | 115-199 |
| 0017W | 20 | GA | | | 10-11 | 33-24-12 | D05902 | | | | SM00017 | | | 9 | 001-099 |
| 0017W | 20 | GA | | | 10-7 | 33-24-12 | D05902 | | | | SM00017 | | | 9 | 115-199 |
| 0018WP | 16 | GA | | | 10-11 | 33-23-11 | D05902 | | | | SM00018 | | | 9 | 001-099 |
| 0018WP | 16 | GA | | | 10-7 | 33-23-11 | D05902 | | | | SM00018 | | | 9 | 115-199 |
| 0019AJ | 20 | GA | | | 10-11 | 35-21-12 | D05902 | | | | SM00019 | | | 9 | 001-099 |
| 0019AJ | 20 | GA | | | 10-7 | 35-21-12 | D05902 | | | | SM00019 | | | 9 | 115-199 |
| 0020K | 18 | GA | | | 10-11 | 35-21-12 | D05902 | | | | SM00020 | | | 9 | 001-099 |
| 0020K | 18 | GA | | | 10-7 | 35-21-12 | D05902 | | | | SM00020 | | | 9 | 115-199 |
| 0021G | 16 | GA | | | 10-7 | 33-24-12 | D05904 | | | | SM00011 | | | 9 | 001-099 |
| 0021G | 16 | GA | | | 10-3 | 33-24-12 | D05904 | | | | SM00011 | | | 9 | 115-199 |
| 0022WV | 22 | GA | | | 10-7 | 33-25-11 | D05904 | | | | SM00012 | | | 9 | 001-099 |
| 0022WV | 22 | GA | | | 10-3 | 33-25-11 | D05904 | | | | SM00012 | | | 9 | 115-199 |
| 0023WG | 22 | GA | | | 10-7 | 33-25-11 | D05904 | | | | SM00013 | | | 9 | 001-099 |
| 0023WG | 22 | GA | | | 10-3 | 33-25-11 | D05904 | | | | SM00013 | | | 9 | 115-199 |
| 0024WO | 22 | GA | | | 10-7 | 33-25-11 | D05904 | | | | SM00014 | | | 9 | 001-099 |
| 0024WO | 22 | GA | | | 10-3 | 33-25-11 | D05904 | | | | SM00014 | | | 9 | 115-199 |
| 0025V | 22 | GA | | | 10-7 | 33-25-11 | D05904 | | | | SM00015 | | | 9 | 001-099 |
| 0025V | 22 | GA | | | 10-3 | 33-25-11 | D05904 | | | | SM00015 | | | 9 | 115-199 |
| 0026WN | 16 | GA | | | 10-7 | 33-23-11 | D05904 | | | | SM00016 | | | 9 | 001-099 |
| 0026WN | 16 | GA | | | 10-3 | 33-23-11 | D05904 | | | | SM00016 | | | 9 | 115-199 |
| 0027W | 20 | GA | | | 10-7 | 33-24-12 | D05904 | | | | SM00017 | | | 9 | 001-099 |
| 0027W | 20 | GA | | | 10-3 | 33-24-12 | D05904 | | | | SM00017 | | | 9 | 115-199 |
| 0028WP | 16 | GA | | | 10-7 | 33-23-11 | D05904 | | | | SM00018 | | | 9 | 001-099 |
| 0028WP | 16 | GA | | | 10-3 | 33-23-11 | D05904 | | | | SM00018 | | | 9 | 115-199 |
| 0029AJ | 20 | GA | | | 10-7 | 35-21-12 | D05904 | | | | SM00019 | | | 9 | 001-099 |
| 0029AJ | 20 | GA | | | 10-3 | 35-21-12 | D05904 | | | | SM00019 | | | 9 | 115-199 |
| 0030K | 18 | GA | | | 10-7 | 35-21-12 | D05904 | | | | SM00020 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0030K | 18 | | GA | | 10-3 | 35-21-12 | D05904 | | 10 | | | SM00020 | | 9 | | 115-199 |
| 0031G | 16 | | GA | | 7-10 | 33-24-12 | D05906 | | 1 | | | SM00031 | | 9 | | 001-099 |
| 0031G | 16 | | GA | | 7-7 | 33-24-12 | D05906 | | 1 | | | SM00031 | | 9 | | 115-199 |
| 0032WV | 22 | | GA | | 7-10 | 33-25-11 | D05906 | | 2 | | | SM00032 | | 9 | | 001-099 |
| 0032WV | 22 | | GA | | 7-7 | 33-25-11 | D05906 | | 2 | | | SM00032 | | 9 | | 115-199 |
| 0033WG | 22 | | GA | | 7-10 | 33-25-11 | D05906 | | 3 | | | SM00033 | | 9 | | 001-099 |
| 0033WG | 22 | | GA | | 7-7 | 33-25-11 | D05906 | | 3 | | | SM00033 | | 9 | | 115-199 |
| 0034WO | 22 | | GA | | 7-10 | 33-25-11 | D05906 | | 4 | | | SM00034 | | 9 | | 001-099 |
| 0034WO | 22 | | GA | | 7-7 | 33-25-11 | D05906 | | 4 | | | SM00034 | | 9 | | 115-199 |
| 0035V | 22 | | GA | | 7-10 | 33-25-11 | D05906 | | 5 | | | SM00035 | | 9 | | 001-099 |
| 0035V | 22 | | GA | | 7-7 | 33-25-11 | D05906 | | 5 | | | SM00035 | | 9 | | 115-199 |
| 0036WN | 16 | | GA | | 7-10 | 33-23-11 | D05906 | | 6 | | | SM00036 | | 9 | | 001-099 |
| 0036WN | 16 | | GA | | 7-7 | 33-23-11 | D05906 | | 6 | | | SM00036 | | 9 | | 115-199 |
| 0037W | 20 | | GA | | 7-10 | 33-24-12 | D05906 | | 7 | | | SM00037 | | 9 | | 001-099 |
| 0037W | 20 | | GA | | 7-7 | 33-24-12 | D05906 | | 7 | | | SM00037 | | 9 | | 115-199 |
| 0038WP | 16 | | GA | | 7-10 | 33-23-11 | D05906 | | 8 | | | SM00038 | | 9 | | 001-099 |
| 0038WP | 16 | | GA | | 7-7 | 33-23-11 | D05906 | | 8 | | | SM00038 | | 9 | | 115-199 |
| 0039AJ | 20 | | GA | | 7-10 | 35-21-12 | D05906 | | 11 | | | SM00039 | | 9 | | 001-099 |
| 0039AJ | 20 | | GA | | 7-7 | 35-21-12 | D05906 | | 11 | | | SM00039 | | 9 | | 115-199 |
| 0040K | 18 | | GA | | 7-10 | 35-21-12 | D05906 | | 10 | | | SM00040 | | 9 | | 001-099 |
| 0040K | 18 | | GA | | 7-7 | 35-21-12 | D05906 | | 10 | | | SM00040 | | 9 | | 115-199 |
| 0051G | 16 | | GA | | 7-0 | 33-24-12 | D05908 | | 1 | | | SM00051 | | 9 | | 001-099 |
| 0051G | 16 | | GA | | 6-9 | 33-24-12 | D05908 | | 1 | | | SM00051 | | 9 | | 115-199 |
| 0052WV | 22 | | GA | | 7-0 | 33-25-11 | D05908 | | 2 | | | SM00052 | | 9 | | 001-099 |
| 0052WV | 22 | | GA | | 6-9 | 33-25-11 | D05908 | | 2 | | | SM00052 | | 9 | | 115-199 |
| 0053WG | 22 | | GA | | 7-0 | 33-25-11 | D05908 | | 3 | | | SM00053 | | 9 | | 001-099 |
| 0053WG | 22 | | GA | | 6-9 | 33-25-11 | D05908 | | 3 | | | SM00053 | | 9 | | 115-199 |
| 0054WO | 22 | | GA | | 7-0 | 33-25-11 | D05908 | | 4 | | | SM00054 | | 9 | | 001-099 |
| 0054WO | 22 | | GA | | 6-9 | 33-25-11 | D05908 | | 4 | | | SM00054 | | 9 | | 115-199 |
| 0055V | 22 | | GA | | 7-0 | 33-25-11 | D05908 | | 5 | | | SM00055 | | 9 | | 001-099 |
| 0055V | 22 | | GA | | 6-9 | 33-25-11 | D05908 | | 5 | | | SM00055 | | 9 | | 115-199 |
| 0056WN | 16 | | GA | | 7-0 | 33-23-11 | D05908 | | 6 | | | SM00056 | | 9 | | 001-099 |
| 0056WN | 16 | | GA | | 6-9 | 33-23-11 | D05908 | | 6 | | | SM00056 | | 9 | | 115-199 |
| 0057W | 20 | | GA | | 7-0 | 33-24-12 | D05908 | | 7 | | | SM00057 | | 9 | | 001-099 |
| 0057W | 20 | | GA | | 6-9 | 33-24-12 | D05908 | | 7 | | | SM00057 | | 9 | | 115-199 |
| 0058WP | 16 | | GA | | 7-0 | 33-23-11 | D05908 | | 8 | | | SM00058 | | 9 | | 001-099 |
| 0058WP | 16 | | GA | | 6-9 | 33-23-11 | D05908 | | 8 | | | SM00058 | | 9 | | 115-199 |
| 0059AJ | 20 | | GA | | 7-0 | 35-21-12 | D05908 | | 11 | | | SM00059 | | 9 | | 001-099 |
| 0059AJ | 20 | | GA | | 6-9 | 35-21-12 | D05908 | | 11 | | | SM00059 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | |
| 0060K | 18 | | GA | | 7-0 | 35-21-12 | D05908 | | 10 | | SM00060 | | 9 | | 001-099 |
| 0060K | 18 | | GA | | 6-9 | 35-21-12 | D05908 | | 10 | | SM00060 | | 9 | | 115-199 |
| 0061G | 16 | | GA | | 7-0 | 33-24-12 | D05910 | | 1 | | SM00051 | | 9 | | 001-099 |
| 0061G | 16 | | GA | | 6-8 | 33-24-12 | D05910 | | 1 | | SM00051 | | 9 | | 115-199 |
| 0062WV | 22 | | GA | | 7-0 | 33-25-11 | D05910 | | 2 | | SM00052 | | 9 | | 001-099 |
| 0062WV | 22 | | GA | | 6-8 | 33-25-11 | D05910 | | 2 | | SM00052 | | 9 | | 115-199 |
| 0063WG | 22 | | GA | | 7-0 | 33-25-11 | D05910 | | 3 | | SM00053 | | 9 | | 001-099 |
| 0063WG | 22 | | GA | | 6-8 | 33-25-11 | D05910 | | 3 | | SM00053 | | 9 | | 115-199 |
| 0064WO | 22 | | GA | | 7-0 | 33-25-11 | D05910 | | 4 | | SM00054 | | 9 | | 001-099 |
| 0064WO | 22 | | GA | | 6-8 | 33-25-11 | D05910 | | 4 | | SM00054 | | 9 | | 115-199 |
| 0065V | 22 | | GA | | 7-0 | 33-25-11 | D05910 | | 5 | | SM00055 | | 9 | | 001-099 |
| 0065V | 22 | | GA | | 6-8 | 33-25-11 | D05910 | | 5 | | SM00055 | | 9 | | 115-199 |
| 0066WN | 16 | | GA | | 7-0 | 33-23-11 | D05910 | | 6 | | SM00056 | | 9 | | 001-099 |
| 0066WN | 16 | | GA | | 6-8 | 33-23-11 | D05910 | | 6 | | SM00056 | | 9 | | 115-199 |
| 0067W | 20 | | GA | | 7-0 | 33-24-12 | D05910 | | 7 | | SM00057 | | 9 | | 001-099 |
| 0067W | 20 | | GA | | 6-8 | 33-24-12 | D05910 | | 7 | | SM00057 | | 9 | | 115-199 |
| 0068WP | 16 | | GA | | 7-0 | 33-23-11 | D05910 | | 8 | | SM00058 | | 9 | | 001-099 |
| 0068WP | 16 | | GA | | 6-8 | 33-23-11 | D05910 | | 8 | | SM00058 | | 9 | | 115-199 |
| 0069AJ | 20 | | GA | | 7-0 | 35-21-12 | D05910 | | 11 | | SM00059 | | 9 | | 001-099 |
| 0069AJ | 20 | | GA | | 6-8 | 35-21-12 | D05910 | | 11 | | SM00059 | | 9 | | 115-199 |
| 0070K | 18 | | GA | | 7-0 | 35-21-12 | D05910 | | 10 | | SM00060 | | 9 | | 001-099 |
| 0070K | 18 | | GA | | 6-8 | 35-21-12 | D05910 | | 10 | | SM00060 | | 9 | | 115-199 |
| 0071G | 16 | | GA | | 8-6 | 33-24-12 | D05912 | | 1 | | SM00071 | | 9 | | 001-099 |
| 0071G | 16 | | GA | | 7-0 | 33-24-12 | D05912 | | 1 | | SM00071 | | 9 | | 115-199 |
| 0072WV | 22 | | GA | | 8-6 | 33-25-11 | D05912 | | 2 | | SM00072 | | 9 | | 001-099 |
| 0072WV | 22 | | GA | | 7-0 | 33-25-11 | D05912 | | 2 | | SM00072 | | 9 | | 115-199 |
| 0073WG | 22 | | GA | | 8-6 | 33-25-11 | D05912 | | 3 | | SM00073 | | 9 | | 001-099 |
| 0073WG | 22 | | GA | | 7-0 | 33-25-11 | D05912 | | 3 | | SM00073 | | 9 | | 115-199 |
| 0074WO | 22 | | GA | | 8-6 | 33-25-11 | D05912 | | 4 | | SM00074 | | 9 | | 001-099 |
| 0074WO | 22 | | GA | | 7-0 | 33-25-11 | D05912 | | 4 | | SM00074 | | 9 | | 115-199 |
| 0075V | 22 | | GA | | 8-6 | 33-25-11 | D05912 | | 5 | | SM00075 | | 9 | | 001-099 |
| 0075V | 22 | | GA | | 7-0 | 33-25-11 | D05912 | | 5 | | SM00075 | | 9 | | 115-199 |
| 0076WN | 16 | | GA | | 8-6 | 33-23-11 | D05912 | | 6 | | SM00076 | | 9 | | 001-099 |
| 0076WN | 16 | | GA | | 7-0 | 33-23-11 | D05912 | | 6 | | SM00076 | | 9 | | 115-199 |
| 0077W | 20 | | GA | | 8-6 | 33-24-12 | D05912 | | 7 | | SM00077 | | 9 | | 001-099 |
| 0077W | 20 | | GA | | 7-0 | 33-24-12 | D05912 | | 7 | | SM00077 | | 9 | | 115-199 |
| 0078WP | 16 | | GA | | 8-6 | 33-23-11 | D05912 | | 8 | | SM00078 | | 9 | | 001-099 |
| 0078WP | 16 | | GA | | 7-0 | 33-23-11 | D05912 | | 8 | | SM00078 | | 9 | | 115-199 |
| 0079AJ | 20 | | GA | | 8-6 | 35-21-12 | D05912 | | 11 | | SM00079 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|-------|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|--|-------------|
| | GA | CO TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0079AJ | 20 | GA | | 7-0 | 35-21-12 | D05912 | | 11 | | | SM00079 | | 9 | | 115-199 |
| 0080K | 18 | GA | | 8-6 | 35-21-12 | D05912 | | 10 | | | SM00080 | | 9 | | 001-099 |
| 0080K | 18 | GA | | 7-0 | 35-21-12 | D05912 | | 10 | | | SM00080 | | 9 | | 115-199 |
| 0081G | 16 | GA | | 9-3 | 33-24-12 | D05914 | | 1 | | | SM00071 | | 9 | | 001-099 |
| 0081G | 16 | GA | | 8-11 | 33-24-12 | D05914 | | 1 | | | SM00071 | | 9 | | 115-199 |
| 0082WV | 22 | GA | | 9-3 | 33-25-11 | D05914 | | 2 | | | SM00072 | | 9 | | 001-099 |
| 0082WV | 22 | GA | | 8-11 | 33-25-11 | D05914 | | 2 | | | SM00072 | | 9 | | 115-199 |
| 0083WG | 22 | GA | | 9-3 | 33-25-11 | D05914 | | 3 | | | SM00073 | | 9 | | 001-099 |
| 0083WG | 22 | GA | | 8-11 | 33-25-11 | D05914 | | 3 | | | SM00073 | | 9 | | 115-199 |
| 0084WO | 22 | GA | | 9-3 | 33-25-11 | D05914 | | 4 | | | SM00074 | | 9 | | 001-099 |
| 0084WO | 22 | GA | | 8-11 | 33-25-11 | D05914 | | 4 | | | SM00074 | | 9 | | 115-199 |
| 0085V | 22 | GA | | 9-3 | 33-25-11 | D05914 | | 5 | | | SM00075 | | 9 | | 001-099 |
| 0085V | 22 | GA | | 8-11 | 33-25-11 | D05914 | | 5 | | | SM00075 | | 9 | | 115-199 |
| 0086WN | 16 | GA | | 9-3 | 33-23-11 | D05914 | | 6 | | | SM00076 | | 9 | | 001-099 |
| 0086WN | 16 | GA | | 8-11 | 33-23-11 | D05914 | | 6 | | | SM00076 | | 9 | | 115-199 |
| 0087W | 20 | GA | | 9-3 | 33-24-12 | D05914 | | 7 | | | SM00077 | | 9 | | 001-099 |
| 0087W | 20 | GA | | 8-11 | 33-24-12 | D05914 | | 7 | | | SM00077 | | 9 | | 115-199 |
| 0088WP | 16 | GA | | 9-3 | 33-23-11 | D05914 | | 8 | | | SM00078 | | 9 | | 001-099 |
| 0088WP | 16 | GA | | 8-11 | 33-23-11 | D05914 | | 8 | | | SM00078 | | 9 | | 115-199 |
| 0089AJ | 20 | GA | | 9-3 | 35-21-12 | D05914 | | 11 | | | SM00079 | | 9 | | 001-099 |
| 0089AJ | 20 | GA | | 8-11 | 35-21-12 | D05914 | | 11 | | | SM00079 | | 9 | | 115-199 |
| 0090K | 18 | GA | | 9-3 | 35-21-12 | D05914 | | 10 | | | SM00080 | | 9 | | 001-099 |
| 0090K | 18 | GA | | 8-11 | 35-21-12 | D05914 | | 10 | | | SM00080 | | 9 | | 115-199 |
| 0091G | 16 | GA | | 7-7 | 33-24-12 | D05916 | | 1 | | | SM00091 | | 9 | | 001-099 |
| 0091G | 16 | GA | | 7-4 | 33-24-12 | D05916 | | 1 | | | SM00091 | | 9 | | 115-199 |
| 0092WV | 22 | GA | | 7-7 | 33-25-11 | D05916 | | 2 | | | SM00092 | | 9 | | 001-099 |
| 0092WV | 22 | GA | | 7-4 | 33-25-11 | D05916 | | 2 | | | SM00092 | | 9 | | 115-199 |
| 0093WG | 22 | GA | | 7-7 | 33-25-11 | D05916 | | 3 | | | SM00093 | | 9 | | 001-099 |
| 0093WG | 22 | GA | | 7-4 | 33-25-11 | D05916 | | 3 | | | SM00093 | | 9 | | 115-199 |
| 0094WO | 22 | GA | | 7-7 | 33-25-11 | D05916 | | 4 | | | SM00094 | | 9 | | 001-099 |
| 0094WO | 22 | GA | | 7-4 | 33-25-11 | D05916 | | 4 | | | SM00094 | | 9 | | 115-199 |
| 0095V | 22 | GA | | 7-7 | 33-25-11 | D05916 | | 5 | | | SM00095 | | 9 | | 001-099 |
| 0095V | 22 | GA | | 7-4 | 33-25-11 | D05916 | | 5 | | | SM00095 | | 9 | | 115-199 |
| 0096WN | 16 | GA | | 7-7 | 33-23-11 | D05916 | | 6 | | | SM00096 | | 9 | | 001-099 |
| 0096WN | 16 | GA | | 7-4 | 33-23-11 | D05916 | | 6 | | | SM00096 | | 9 | | 115-199 |
| 0097W | 20 | GA | | 7-7 | 33-24-12 | D05916 | | 7 | | | SM00097 | | 9 | | 001-099 |
| 0097W | 20 | GA | | 7-4 | 33-24-12 | D05916 | | 7 | | | SM00097 | | 9 | | 115-199 |
| 0098WP | 16 | GA | | 7-7 | 33-23-11 | D05916 | | 8 | | | SM00098 | | 9 | | 001-099 |
| 0098WP | 16 | GA | | 7-4 | 33-23-11 | D05916 | | 8 | | | SM00098 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0099AJ | 20 | | GA | 7-7 | 35-21-12 | D05916 | | 11 | | | SM00099 | | 9 | | 001-099 |
| 0099AJ | 20 | | GA | 7-4 | 35-21-12 | D05916 | | 11 | | | SM00099 | | 9 | | 115-199 |
| 0100K | 18 | | GA | 7-7 | 35-21-12 | D05916 | | 10 | | | SM00100 | | 9 | | 001-099 |
| 0100K | 18 | | GA | 7-4 | 35-21-12 | D05916 | | 10 | | | SM00100 | | 9 | | 115-199 |
| 0101G | 16 | | GA | 8-10 | 33-24-12 | D05918 | | 1 | | | SM00091 | | 9 | | 001-099 |
| 0101G | 16 | | GA | 8-7 | 33-24-12 | D05918 | | 1 | | | SM00091 | | 9 | | 115-199 |
| 0102WV | 22 | | GA | 8-10 | 33-25-11 | D05918 | | 2 | | | SM00092 | | 9 | | 001-099 |
| 0102WV | 22 | | GA | 8-7 | 33-25-11 | D05918 | | 2 | | | SM00092 | | 9 | | 115-199 |
| 0103WG | 22 | | GA | 8-10 | 33-25-11 | D05918 | | 3 | | | SM00093 | | 9 | | 001-099 |
| 0103WG | 22 | | GA | 8-7 | 33-25-11 | D05918 | | 3 | | | SM00093 | | 9 | | 115-199 |
| 0104WO | 22 | | GA | 8-10 | 33-25-11 | D05918 | | 4 | | | SM00094 | | 9 | | 001-099 |
| 0104WO | 22 | | GA | 8-7 | 33-25-11 | D05918 | | 4 | | | SM00094 | | 9 | | 115-199 |
| 0105V | 22 | | GA | 8-10 | 33-25-11 | D05918 | | 5 | | | SM00095 | | 9 | | 001-099 |
| 0105V | 22 | | GA | 8-7 | 33-25-11 | D05918 | | 5 | | | SM00095 | | 9 | | 115-199 |
| 0106WN | 16 | | GA | 8-10 | 33-23-11 | D05918 | | 6 | | | SM00096 | | 9 | | 001-099 |
| 0106WN | 16 | | GA | 8-7 | 33-23-11 | D05918 | | 6 | | | SM00096 | | 9 | | 115-199 |
| 0107W | 20 | | GA | 8-10 | 33-24-12 | D05918 | | 7 | | | SM00097 | | 9 | | 001-099 |
| 0107W | 20 | | GA | 8-7 | 33-24-12 | D05918 | | 7 | | | SM00097 | | 9 | | 115-199 |
| 0108WP | 16 | | GA | 8-10 | 33-23-11 | D05918 | | 8 | | | SM00098 | | 9 | | 001-099 |
| 0108WP | 16 | | GA | 8-7 | 33-23-11 | D05918 | | 8 | | | SM00098 | | 9 | | 115-199 |
| 0109AJ | 20 | | GA | 8-10 | 35-21-12 | D05918 | | 11 | | | SM00099 | | 9 | | 001-099 |
| 0109AJ | 20 | | GA | 8-7 | 35-21-12 | D05918 | | 11 | | | SM00099 | | 9 | | 115-199 |
| 0110K | 18 | | GA | 8-10 | 35-21-12 | D05918 | | 10 | | | SM00100 | | 9 | | 001-099 |
| 0110K | 18 | | GA | 8-7 | 35-21-12 | D05918 | | 10 | | | SM00100 | | 9 | | 115-199 |
| 0111G | 16 | | GA | 8-9 | 33-24-12 | D05920 | | 1 | | | SM00111 | | 9 | | 001-099 |
| 0111G | 16 | | GA | 8-5 | 33-24-12 | D05920 | | 1 | | | SM00111 | | 9 | | 115-199 |
| 0112WV | 22 | | GA | 8-9 | 33-25-11 | D05920 | | 2 | | | SM00112 | | 9 | | 001-099 |
| 0112WV | 22 | | GA | 8-5 | 33-25-11 | D05920 | | 2 | | | SM00112 | | 9 | | 115-199 |
| 0113WG | 22 | | GA | 8-9 | 33-25-11 | D05920 | | 3 | | | SM00113 | | 9 | | 001-099 |
| 0113WG | 22 | | GA | 8-5 | 33-25-11 | D05920 | | 3 | | | SM00113 | | 9 | | 115-199 |
| 0114WO | 22 | | GA | 8-9 | 33-25-11 | D05920 | | 4 | | | SM00114 | | 9 | | 001-099 |
| 0114WO | 22 | | GA | 8-5 | 33-25-11 | D05920 | | 4 | | | SM00114 | | 9 | | 115-199 |
| 0115V | 22 | | GA | 8-9 | 33-25-11 | D05920 | | 5 | | | SM00115 | | 9 | | 001-099 |
| 0115V | 22 | | GA | 8-5 | 33-25-11 | D05920 | | 5 | | | SM00115 | | 9 | | 115-199 |
| 0116WN | 16 | | GA | 8-9 | 33-23-11 | D05920 | | 6 | | | SM00116 | | 9 | | 001-099 |
| 0116WN | 16 | | GA | 8-5 | 33-23-11 | D05920 | | 6 | | | SM00116 | | 9 | | 115-199 |
| 0117W | 20 | | GA | 8-9 | 33-24-12 | D05920 | | 7 | | | SM00117 | | 9 | | 001-099 |
| 0117W | 20 | | GA | 8-5 | 33-24-12 | D05920 | | 7 | | | SM00117 | | 9 | | 115-199 |
| 0118WP | 16 | | GA | 8-9 | 33-23-11 | D05920 | | 8 | | | SM00118 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0118WP | 16 | | GA | | 8-5 | 33-23-11 | | D05920 | | | | SM00118 | | | 9 | 115-199 |
| 0119AJ | 20 | | GA | | 8-9 | 35-21-12 | | D05920 | | | | SM00119 | | | 9 | 001-099 |
| 0119AJ | 20 | | GA | | 8-5 | 35-21-12 | | D05920 | | | | SM00119 | | | 9 | 115-199 |
| 0120K | 18 | | GA | | 8-9 | 35-21-12 | | D05920 | | | | SM00120 | | | 9 | 001-099 |
| 0120K | 18 | | GA | | 8-5 | 35-21-12 | | D05920 | | | | SM00120 | | | 9 | 115-199 |
| 0121G | 16 | | GA | | 7-6 | 33-24-12 | | D05922 | | | | SM00111 | | | 9 | 001-099 |
| 0121G | 16 | | GA | | 7-1 | 33-24-12 | | D05922 | | | | SM00111 | | | 9 | 115-199 |
| 0122WV | 22 | | GA | | 7-6 | 33-25-11 | | D05922 | | | | SM00112 | | | 9 | 001-099 |
| 0122WV | 22 | | GA | | 7-1 | 33-25-11 | | D05922 | | | | SM00112 | | | 9 | 115-199 |
| 0123WG | 22 | | GA | | 7-6 | 33-25-11 | | D05922 | | | | SM00113 | | | 9 | 001-099 |
| 0123WG | 22 | | GA | | 7-1 | 33-25-11 | | D05922 | | | | SM00113 | | | 9 | 115-199 |
| 0124WO | 22 | | GA | | 7-6 | 33-25-11 | | D05922 | | | | SM00114 | | | 9 | 001-099 |
| 0124WO | 22 | | GA | | 7-1 | 33-25-11 | | D05922 | | | | SM00114 | | | 9 | 115-199 |
| 0125V | 22 | | GA | | 7-6 | 33-25-11 | | D05922 | | | | SM00115 | | | 9 | 001-099 |
| 0125V | 22 | | GA | | 7-1 | 33-25-11 | | D05922 | | | | SM00115 | | | 9 | 115-199 |
| 0126WN | 16 | | GA | | 7-6 | 33-23-11 | | D05922 | | | | SM00116 | | | 9 | 001-099 |
| 0126WN | 16 | | GA | | 7-1 | 33-23-11 | | D05922 | | | | SM00116 | | | 9 | 115-199 |
| 0127W | 20 | | GA | | 7-6 | 33-24-12 | | D05922 | | | | SM00117 | | | 9 | 001-099 |
| 0127W | 20 | | GA | | 7-1 | 33-24-12 | | D05922 | | | | SM00117 | | | 9 | 115-199 |
| 0128WP | 16 | | GA | | 7-6 | 33-23-11 | | D05922 | | | | SM00118 | | | 9 | 001-099 |
| 0128WP | 16 | | GA | | 7-1 | 33-23-11 | | D05922 | | | | SM00118 | | | 9 | 115-199 |
| 0129AJ | 20 | | GA | | 7-6 | 35-21-12 | | D05922 | | | | SM00119 | | | 9 | 001-099 |
| 0129AJ | 20 | | GA | | 7-1 | 35-21-12 | | D05922 | | | | SM00119 | | | 9 | 115-199 |
| 0130K | 18 | | GA | | 7-6 | 35-21-12 | | D05922 | | | | SM00120 | | | 9 | 001-099 |
| 0130K | 18 | | GA | | 7-1 | 35-21-12 | | D05922 | | | | SM00120 | | | 9 | 115-199 |
| 0131G | 16 | | GA | | 9-11 | 33-24-12 | | D05924 | | | | SM00131 | | | 9 | 001-099 |
| 0131G | 16 | | GA | | 9-7 | 33-24-12 | | D05924 | | | | SM00131 | | | 9 | 115-199 |
| 0132WV | 22 | | GA | | 9-11 | 33-25-11 | | D05924 | | | | SM00132 | | | 9 | 001-099 |
| 0132WV | 22 | | GA | | 9-7 | 33-25-11 | | D05924 | | | | SM00132 | | | 9 | 115-199 |
| 0133WG | 22 | | GA | | 9-11 | 33-25-11 | | D05924 | | | | SM00133 | | | 9 | 001-099 |
| 0133WG | 22 | | GA | | 9-7 | 33-25-11 | | D05924 | | | | SM00133 | | | 9 | 115-199 |
| 0134WO | 22 | | GA | | 9-11 | 33-25-11 | | D05924 | | | | SM00134 | | | 9 | 001-099 |
| 0134WO | 22 | | GA | | 9-7 | 33-25-11 | | D05924 | | | | SM00134 | | | 9 | 115-199 |
| 0135V | 22 | | GA | | 9-11 | 33-25-11 | | D05924 | | | | SM00135 | | | 9 | 001-099 |
| 0135V | 22 | | GA | | 9-7 | 33-25-11 | | D05924 | | | | SM00135 | | | 9 | 115-199 |
| 0136WN | 16 | | GA | | 9-11 | 33-23-11 | | D05924 | | | | SM00136 | | | 9 | 001-099 |
| 0136WN | 16 | | GA | | 9-7 | 33-23-11 | | D05924 | | | | SM00136 | | | 9 | 115-199 |
| 0137W | 20 | | GA | | 9-11 | 33-24-12 | | D05924 | | | | SM00137 | | | 9 | 001-099 |
| 0137W | 20 | | GA | | 9-7 | 33-24-12 | | D05924 | | | | SM00137 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|-------------|---------|-------|------|------|---------|-------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0138WP | 16 | | GA | 9-11 | 33-23-11 | D05924 | | 8 | | SM00138 | | 9 | | 001-099 | |
| 0138WP | 16 | | GA | 9-7 | 33-23-11 | D05924 | | 8 | | SM00138 | | 9 | | 115-199 | |
| 0139AJ | 20 | | GA | 9-11 | 35-21-12 | D05924 | | 11 | | SM00139 | | 9 | | 001-099 | |
| 0139AJ | 20 | | GA | 9-7 | 35-21-12 | D05924 | | 11 | | SM00139 | | 9 | | 115-199 | |
| 0140K | 18 | | GA | 9-11 | 35-21-12 | D05924 | | 10 | | SM00140 | | 9 | | 001-099 | |
| 0140K | 18 | | GA | 9-7 | 35-21-12 | D05924 | | 10 | | SM00140 | | 9 | | 115-199 | |
| 0141G | 16 | | GA | 7-11 | 33-24-12 | D05926 | | 1 | | SM00131 | | 9 | | 001-099 | |
| 0141G | 16 | | GA | 7-7 | 33-24-12 | D05926 | | 1 | | SM00131 | | 9 | | 115-199 | |
| 0142WV | 22 | | GA | 7-11 | 33-25-11 | D05926 | | 2 | | SM00132 | | 9 | | 001-099 | |
| 0142WV | 22 | | GA | 7-7 | 33-25-11 | D05926 | | 2 | | SM00132 | | 9 | | 115-199 | |
| 0143WG | 22 | | GA | 7-11 | 33-25-11 | D05926 | | 3 | | SM00133 | | 9 | | 001-099 | |
| 0143WG | 22 | | GA | 7-7 | 33-25-11 | D05926 | | 3 | | SM00133 | | 9 | | 115-199 | |
| 0144WO | 22 | | GA | 7-11 | 33-25-11 | D05926 | | 4 | | SM00134 | | 9 | | 001-099 | |
| 0144WO | 22 | | GA | 7-7 | 33-25-11 | D05926 | | 4 | | SM00134 | | 9 | | 115-199 | |
| 0145V | 22 | | GA | 7-11 | 33-25-11 | D05926 | | 5 | | SM00135 | | 9 | | 001-099 | |
| 0145V | 22 | | GA | 7-7 | 33-25-11 | D05926 | | 5 | | SM00135 | | 9 | | 115-199 | |
| 0146WN | 16 | | GA | 7-11 | 33-23-11 | D05926 | | 6 | | SM00136 | | 9 | | 001-099 | |
| 0146WN | 16 | | GA | 7-7 | 33-23-11 | D05926 | | 6 | | SM00136 | | 9 | | 115-199 | |
| 0147W | 20 | | GA | 7-11 | 33-24-12 | D05926 | | 7 | | SM00137 | | 9 | | 001-099 | |
| 0147W | 20 | | GA | 7-7 | 33-24-12 | D05926 | | 7 | | SM00137 | | 9 | | 115-199 | |
| 0148WP | 16 | | GA | 7-11 | 33-23-11 | D05926 | | 8 | | SM00138 | | 9 | | 001-099 | |
| 0148WP | 16 | | GA | 7-7 | 33-23-11 | D05926 | | 8 | | SM00138 | | 9 | | 115-199 | |
| 0149AJ | 20 | | GA | 7-11 | 35-21-12 | D05926 | | 11 | | SM00139 | | 9 | | 001-099 | |
| 0149AJ | 20 | | GA | 7-7 | 35-21-12 | D05926 | | 11 | | SM00139 | | 9 | | 115-199 | |
| 0150K | 18 | | GA | 7-11 | 35-21-12 | D05926 | | 10 | | SM00140 | | 9 | | 001-099 | |
| 0150K | 18 | | GA | 7-7 | 35-21-12 | D05926 | | 10 | | SM00140 | | 9 | | 115-199 | |
| 0151G | 16 | | GA | 9-0 | 33-24-12 | D05928 | | 1 | | SM00131 | | 9 | | 001-099 | |
| 0151G | 16 | | GA | 8-4 | 33-24-12 | D05928 | | 1 | | SM00131 | | 9 | | 115-199 | |
| 0152WV | 22 | | GA | 9-0 | 33-25-11 | D05928 | | 2 | | SM00132 | | 9 | | 001-099 | |
| 0152WV | 22 | | GA | 8-4 | 33-25-11 | D05928 | | 2 | | SM00132 | | 9 | | 115-199 | |
| 0153WG | 22 | | GA | 9-0 | 33-25-11 | D05928 | | 3 | | SM00133 | | 9 | | 001-099 | |
| 0153WG | 22 | | GA | 8-4 | 33-25-11 | D05928 | | 3 | | SM00133 | | 9 | | 115-199 | |
| 0154WO | 22 | | GA | 9-0 | 33-25-11 | D05928 | | 4 | | SM00134 | | 9 | | 001-099 | |
| 0154WO | 22 | | GA | 8-4 | 33-25-11 | D05928 | | 4 | | SM00134 | | 9 | | 115-199 | |
| 0155V | 22 | | GA | 9-0 | 33-25-11 | D05928 | | 5 | | SM00135 | | 9 | | 001-099 | |
| 0155V | 22 | | GA | 8-4 | 33-25-11 | D05928 | | 5 | | SM00135 | | 9 | | 115-199 | |
| 0156WN | 16 | | GA | 9-0 | 33-23-11 | D05928 | | 6 | | SM00136 | | 9 | | 001-099 | |
| 0156WN | 16 | | GA | 8-4 | 33-23-11 | D05928 | | 6 | | SM00136 | | 9 | | 115-199 | |
| 0157W | 20 | | GA | 9-0 | 33-24-12 | D05928 | | 7 | | SM00137 | | 9 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0157W | 20 | | GA | | 8-4 | 33-24-12 | | D05928 | | | | SM00137 | | 9 | | 115-199 |
| 0158WP | 16 | | GA | | 9-0 | 33-23-11 | | D05928 | | | | SM00138 | | 9 | | 001-099 |
| 0158WP | 16 | | GA | | 8-4 | 33-23-11 | | D05928 | | | | SM00138 | | 9 | | 115-199 |
| 0159AJ | 20 | | GA | | 9-0 | 35-21-12 | | D05928 | | 11 | | SM00139 | | 9 | | 001-099 |
| 0159AJ | 20 | | GA | | 8-4 | 35-21-12 | | D05928 | | 11 | | SM00139 | | 9 | | 115-199 |
| 0160K | 18 | | GA | | 9-0 | 35-21-12 | | D05928 | | 10 | | SM00140 | | 9 | | 001-099 |
| 0160K | 18 | | GA | | 8-4 | 35-21-12 | | D05928 | | 10 | | SM00140 | | 9 | | 115-199 |
| 0161G | 16 | | GA | | 3-6 | 33-24-12 | | D05930 | | 1 | | SM00171 | | 9 | | 001-099 |
| 0161G | 16 | | GA | | 3-3 | 33-24-12 | | D05930 | | 1 | | SM00171 | | 9 | | 115-199 |
| 0162WV | 22 | | GA | | 3-6 | 33-25-11 | | D05930 | | 2 | | SM00172 | | 9 | | 001-099 |
| 0162WV | 22 | | GA | | 3-3 | 33-25-11 | | D05930 | | 2 | | SM00172 | | 9 | | 115-199 |
| 0163WG | 22 | | GA | | 3-6 | 33-25-11 | | D05930 | | 3 | | SM00173 | | 9 | | 001-099 |
| 0163WG | 22 | | GA | | 3-3 | 33-25-11 | | D05930 | | 3 | | SM00173 | | 9 | | 115-199 |
| 0164WO | 22 | | GA | | 3-6 | 33-25-11 | | D05930 | | 4 | | SM00174 | | 9 | | 001-099 |
| 0164WO | 22 | | GA | | 3-3 | 33-25-11 | | D05930 | | 4 | | SM00174 | | 9 | | 115-199 |
| 0165V | 22 | | GA | | 3-6 | 33-25-11 | | D05930 | | 5 | | SM00175 | | 9 | | 001-099 |
| 0165V | 22 | | GA | | 3-3 | 33-25-11 | | D05930 | | 5 | | SM00175 | | 9 | | 115-199 |
| 0166WN | 16 | | GA | | 3-6 | 33-23-12 | | D05930 | | 6 | | SM00176 | | 9 | | 001-099 |
| 0166WN | 16 | | GA | | 3-3 | 33-23-12 | | D05930 | | 6 | | SM00176 | | 9 | | 115-199 |
| 0167W | 20 | | GA | | 3-6 | 33-24-12 | | D05930 | | 7 | | SM00177 | | 9 | | 001-099 |
| 0167W | 20 | | GA | | 3-3 | 33-24-12 | | D05930 | | 7 | | SM00177 | | 9 | | 115-199 |
| 0168WP | 16 | | GA | | 3-6 | 33-23-12 | | D05930 | | 8 | | SM00178 | | 9 | | 001-099 |
| 0168WP | 16 | | GA | | 3-3 | 33-23-12 | | D05930 | | 8 | | SM00178 | | 9 | | 115-199 |
| 0169AJ | 20 | | GA | | 3-6 | 35-21-12 | | D05930 | | 11 | | SM00179 | | 9 | | 001-099 |
| 0169AJ | 20 | | GA | | 3-3 | 35-21-12 | | D05930 | | 11 | | SM00179 | | 9 | | 115-199 |
| 0170K | 18 | | GA | | 3-6 | 35-21-12 | | D05930 | | 10 | | SM00180 | | 9 | | 001-099 |
| 0170K | 18 | | GA | | 3-3 | 35-21-12 | | D05930 | | 10 | | SM00180 | | 9 | | 115-199 |
| 0171G | 16 | | GA | | 3-6 | 33-24-12 | | D05932 | | 1 | | SM00171 | | 9 | | 001-099 |
| 0171G | 16 | | GA | | 3-2 | 33-24-12 | | D05932 | | 1 | | SM00171 | | 9 | | 115-199 |
| 0172WV | 22 | | GA | | 3-6 | 33-25-11 | | D05932 | | 2 | | SM00172 | | 9 | | 001-099 |
| 0172WV | 22 | | GA | | 3-2 | 33-25-11 | | D05932 | | 2 | | SM00172 | | 9 | | 115-199 |
| 0173WG | 22 | | GA | | 3-6 | 33-25-11 | | D05932 | | 3 | | SM00173 | | 9 | | 001-099 |
| 0173WG | 22 | | GA | | 3-2 | 33-25-11 | | D05932 | | 3 | | SM00173 | | 9 | | 115-199 |
| 0174WO | 22 | | GA | | 3-6 | 33-25-11 | | D05932 | | 4 | | SM00174 | | 9 | | 001-099 |
| 0174WO | 22 | | GA | | 3-2 | 33-25-11 | | D05932 | | 4 | | SM00174 | | 9 | | 115-199 |
| 0175V | 22 | | GA | | 3-6 | 33-25-11 | | D05932 | | 5 | | SM00175 | | 9 | | 001-099 |
| 0175V | 22 | | GA | | 3-2 | 33-25-11 | | D05932 | | 5 | | SM00175 | | 9 | | 115-199 |
| 0176WN | 16 | | GA | | 3-6 | 33-23-12 | | D05932 | | 6 | | SM00176 | | 9 | | 001-099 |
| 0176WN | 16 | | GA | | 3-2 | 33-23-12 | | D05932 | | 6 | | SM00176 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|--|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | |
| 0177W | 20 | | GA | 3-6 | 33-24-12 | D05932 | | 7 | | SM00177 | | 9 | | 001-099 |
| 0177W | 20 | | GA | 3-2 | 33-24-12 | D05932 | | 7 | | SM00177 | | 9 | | 115-199 |
| 0178WP | 16 | | GA | 3-6 | 33-23-12 | D05932 | | 8 | | SM00178 | | 9 | | 001-099 |
| 0178WP | 16 | | GA | 3-2 | 33-23-12 | D05932 | | 8 | | SM00178 | | 9 | | 115-199 |
| 0179AJ | 20 | | GA | 3-6 | 35-21-12 | D05932 | | 11 | | SM00179 | | 9 | | 001-099 |
| 0179AJ | 20 | | GA | 3-2 | 35-21-12 | D05932 | | 11 | | SM00179 | | 9 | | 115-199 |
| 0180K | 18 | | GA | 3-6 | 35-21-12 | D05932 | | 10 | | SM00180 | | 9 | | 001-099 |
| 0180K | 18 | | GA | 3-2 | 35-21-12 | D05932 | | 10 | | SM00180 | | 9 | | 115-199 |
| 0181G | 16 | | GA | 9-1 | 33-24-12 | D05934 | | 1 | | SM00191 | | 9 | | 001-099 |
| 0181G | 16 | | GA | 8-9 | 33-24-12 | D05934 | | 1 | | SM00191 | | 9 | | 115-199 |
| 0182WV | 22 | | GA | 9-1 | 33-25-12 | D05934 | | 2 | | SM00192 | | 9 | | 001-099 |
| 0182WV | 22 | | GA | 8-9 | 33-25-12 | D05934 | | 2 | | SM00192 | | 9 | | 115-199 |
| 0183WG | 22 | | GA | 9-1 | 33-25-12 | D05934 | | 3 | | SM00193 | | 9 | | 001-099 |
| 0183WG | 22 | | GA | 8-9 | 33-25-12 | D05934 | | 3 | | SM00193 | | 9 | | 115-199 |
| 0184WO | 22 | | GA | 9-1 | 33-25-12 | D05934 | | 4 | | SM00194 | | 9 | | 001-099 |
| 0184WO | 22 | | GA | 8-9 | 33-25-12 | D05934 | | 4 | | SM00194 | | 9 | | 115-199 |
| 0185V | 22 | | GA | 9-1 | 33-25-12 | D05934 | | 5 | | SM00195 | | 9 | | 001-099 |
| 0185V | 22 | | GA | 8-9 | 33-25-12 | D05934 | | 5 | | SM00195 | | 9 | | 115-199 |
| 0186WN | 16 | | GA | 9-1 | 33-23-12 | D05934 | | 6 | | SM00196 | | 9 | | 001-099 |
| 0186WN | 16 | | GA | 8-9 | 33-23-12 | D05934 | | 6 | | SM00196 | | 9 | | 115-199 |
| 0187W | 20 | | GA | 9-1 | 33-24-12 | D05934 | | 7 | | SM00197 | | 9 | | 001-099 |
| 0187W | 20 | | GA | 8-9 | 33-24-12 | D05934 | | 7 | | SM00197 | | 9 | | 115-199 |
| 0188WP | 16 | | GA | 9-1 | 33-23-12 | D05934 | | 8 | | SM00198 | | 9 | | 001-099 |
| 0188WP | 16 | | GA | 8-9 | 33-23-12 | D05934 | | 8 | | SM00198 | | 9 | | 115-199 |
| 0189AJ | 20 | | GA | 9-1 | 35-21-12 | D05934 | | 11 | | SM00199 | | 9 | | 001-099 |
| 0189AJ | 20 | | GA | 8-9 | 35-21-12 | D05934 | | 11 | | SM00199 | | 9 | | 115-199 |
| 0190K | 18 | | GA | 9-1 | 35-21-12 | D05934 | | 10 | | SM00200 | | 9 | | 001-099 |
| 0190K | 18 | | GA | 8-9 | 35-21-12 | D05934 | | 10 | | SM00200 | | 9 | | 115-199 |
| 0191G | 16 | | GA | 8-1 | 33-24-12 | D05936 | | 1 | | SM00191 | | 9 | | 001-099 |
| 0191G | 16 | | GA | 7-9 | 33-24-12 | D05936 | | 1 | | SM00191 | | 9 | | 115-199 |
| 0192WV | 22 | | GA | 8-1 | 33-25-12 | D05936 | | 2 | | SM00192 | | 9 | | 001-099 |
| 0192WV | 22 | | GA | 7-9 | 33-25-12 | D05936 | | 2 | | SM00192 | | 9 | | 115-199 |
| 0193WG | 22 | | GA | 8-1 | 33-25-12 | D05936 | | 3 | | SM00193 | | 9 | | 001-099 |
| 0193WG | 22 | | GA | 7-9 | 33-25-12 | D05936 | | 3 | | SM00193 | | 9 | | 115-199 |
| 0194WO | 22 | | GA | 8-1 | 33-25-12 | D05936 | | 4 | | SM00194 | | 9 | | 001-099 |
| 0194WO | 22 | | GA | 7-9 | 33-25-12 | D05936 | | 4 | | SM00194 | | 9 | | 115-199 |
| 0195V | 22 | | GA | 8-1 | 33-25-12 | D05936 | | 5 | | SM00195 | | 9 | | 001-099 |
| 0195V | 22 | | GA | 7-9 | 33-25-12 | D05936 | | 5 | | SM00195 | | 9 | | 115-199 |
| 0196WN | 16 | | GA | 8-1 | 33-23-12 | D05936 | | 6 | | SM00196 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | | |
| 0196WN | 16 | | GA | | 7-9 | 33-23-12 | | D05936 | | | 6 | | SM00196 | | 9 | | 115-199 |
| 0197W | 20 | | GA | | 8-1 | 33-24-12 | | D05936 | | | 7 | | SM00197 | | 9 | | 001-099 |
| 0197W | 20 | | GA | | 7-9 | 33-24-12 | | D05936 | | | 7 | | SM00197 | | 9 | | 115-199 |
| 0198WP | 16 | | GA | | 8-1 | 33-23-12 | | D05936 | | | 8 | | SM00198 | | 9 | | 001-099 |
| 0198WP | 16 | | GA | | 7-9 | 33-23-12 | | D05936 | | | 8 | | SM00198 | | 9 | | 115-199 |
| 0199AJ | 20 | | GA | | 8-1 | 35-21-12 | | D05936 | | | 11 | | SM00199 | | 9 | | 001-099 |
| 0199AJ | 20 | | GA | | 7-9 | 35-21-12 | | D05936 | | | 11 | | SM00199 | | 9 | | 115-199 |
| 0200K | 18 | | GA | | 8-1 | 35-21-12 | | D05936 | | | 10 | | SM00200 | | 9 | | 001-099 |
| 0200K | 18 | | GA | | 7-9 | 35-21-12 | | D05936 | | | 10 | | SM00200 | | 9 | | 115-199 |
| 0201G | 16 | | GA | | 8-4 | 33-24-12 | | D05938 | | | 1 | | SM00211 | | 9 | | 001-099 |
| 0201G | 16 | | GA | | 7-11 | 33-24-12 | | D05938 | | | 1 | | SM00211 | | 9 | | 115-199 |
| 0202WV | 22 | | GA | | 8-4 | 33-25-12 | | D05938 | | | 2 | | SM00212 | | 9 | | 001-099 |
| 0202WV | 22 | | GA | | 7-11 | 33-25-12 | | D05938 | | | 2 | | SM00212 | | 9 | | 115-199 |
| 0203WG | 22 | | GA | | 8-4 | 33-25-12 | | D05938 | | | 3 | | SM00213 | | 9 | | 001-099 |
| 0203WG | 22 | | GA | | 7-11 | 33-25-12 | | D05938 | | | 3 | | SM00213 | | 9 | | 115-199 |
| 0204WO | 22 | | GA | | 8-4 | 33-25-12 | | D05938 | | | 4 | | SM00214 | | 9 | | 001-099 |
| 0204WO | 22 | | GA | | 7-11 | 33-25-12 | | D05938 | | | 4 | | SM00214 | | 9 | | 115-199 |
| 0205V | 22 | | GA | | 8-4 | 33-25-12 | | D05938 | | | 5 | | SM00215 | | 9 | | 001-099 |
| 0205V | 22 | | GA | | 7-11 | 33-25-12 | | D05938 | | | 5 | | SM00215 | | 9 | | 115-199 |
| 0206WN | 16 | | GA | | 8-4 | 33-23-12 | | D05938 | | | 6 | | SM00216 | | 9 | | 001-099 |
| 0206WN | 16 | | GA | | 7-11 | 33-23-12 | | D05938 | | | 6 | | SM00216 | | 9 | | 115-199 |
| 0207W | 20 | | GA | | 8-4 | 33-24-12 | | D05938 | | | 7 | | SM00217 | | 9 | | 001-099 |
| 0207W | 20 | | GA | | 7-11 | 33-24-12 | | D05938 | | | 7 | | SM00217 | | 9 | | 115-199 |
| 0208WP | 16 | | GA | | 8-4 | 33-23-12 | | D05938 | | | 8 | | SM00218 | | 9 | | 001-099 |
| 0208WP | 16 | | GA | | 7-11 | 33-23-12 | | D05938 | | | 8 | | SM00218 | | 9 | | 115-199 |
| 0209AJ | 20 | | GA | | 8-4 | 35-21-12 | | D05938 | | | 11 | | SM00219 | | 9 | | 001-099 |
| 0209AJ | 20 | | GA | | 7-11 | 35-21-12 | | D05938 | | | 11 | | SM00219 | | 9 | | 115-199 |
| 0210K | 18 | | GA | | 8-4 | 35-21-12 | | D05938 | | | 10 | | SM00220 | | 9 | | 001-099 |
| 0210K | 18 | | GA | | 7-11 | 35-21-12 | | D05938 | | | 10 | | SM00220 | | 9 | | 115-199 |
| 0211G | 16 | | GA | | 9-2 | 33-24-12 | | D05940 | | | 1 | | SM00211 | | 9 | | 001-099 |
| 0211G | 16 | | GA | | 8-10 | 33-24-12 | | D05940 | | | 1 | | SM00211 | | 9 | | 115-199 |
| 0212WV | 22 | | GA | | 9-2 | 33-25-12 | | D05940 | | | 2 | | SM00212 | | 9 | | 001-099 |
| 0212WV | 22 | | GA | | 8-10 | 33-25-12 | | D05940 | | | 2 | | SM00212 | | 9 | | 115-199 |
| 0213WG | 22 | | GA | | 9-2 | 33-25-12 | | D05940 | | | 3 | | SM00213 | | 9 | | 001-099 |
| 0213WG | 22 | | GA | | 8-10 | 33-25-12 | | D05940 | | | 3 | | SM00213 | | 9 | | 115-199 |
| 0214WO | 22 | | GA | | 9-2 | 33-25-12 | | D05940 | | | 4 | | SM00214 | | 9 | | 001-099 |
| 0214WO | 22 | | GA | | 8-10 | 33-25-12 | | D05940 | | | 4 | | SM00214 | | 9 | | 115-199 |
| 0215V | 22 | | GA | | 9-2 | 33-25-12 | | D05940 | | | 5 | | SM00215 | | 9 | | 001-099 |
| 0215V | 22 | | GA | | 8-10 | 33-25-12 | | D05940 | | | 5 | | SM00215 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 10

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | |
| 0216WN | 16 | GA | | | 9-2 | 33-23-12 | D05940 | | | | SM00216 | | | 9 | 001-099 |
| 0216WN | 16 | GA | | | 8-10 | 33-23-12 | D05940 | | | | SM00216 | | | 9 | 115-199 |
| 0217W | 20 | GA | | | 9-2 | 33-24-12 | D05940 | | | | SM00217 | | | 9 | 001-099 |
| 0217W | 20 | GA | | | 8-10 | 33-24-12 | D05940 | | | | SM00217 | | | 9 | 115-199 |
| 0218WP | 16 | GA | | | 9-2 | 33-23-12 | D05940 | | | | SM00218 | | | 9 | 001-099 |
| 0218WP | 16 | GA | | | 8-10 | 33-23-12 | D05940 | | | | SM00218 | | | 9 | 115-199 |
| 0219AJ | 20 | GA | | | 9-2 | 35-21-12 | D05940 | | | 11 | SM00219 | | | 9 | 001-099 |
| 0219AJ | 20 | GA | | | 8-10 | 35-21-12 | D05940 | | | 11 | SM00219 | | | 9 | 115-199 |
| 0220K | 18 | GA | | | 9-2 | 35-21-12 | D05940 | | | 10 | SM00220 | | | 9 | 001-099 |
| 0220K | 18 | GA | | | 8-10 | 35-21-12 | D05940 | | | 10 | SM00220 | | | 9 | 115-199 |
| 0221G | 16 | GA | | | 11-1 | 33-24-12 | D05942 | | | 1 | SM00231 | | | 9 | 001-099 |
| 0221G | 16 | GA | | | 10-9 | 33-24-12 | D05942 | | | 1 | SM00231 | | | 9 | 115-199 |
| 0222WV | 22 | GA | | | 11-1 | 33-25-12 | D05942 | | | 2 | SM00232 | | | 9 | 001-099 |
| 0222WV | 22 | GA | | | 10-9 | 33-25-12 | D05942 | | | 2 | SM00232 | | | 9 | 115-199 |
| 0223WG | 22 | GA | | | 11-1 | 33-25-12 | D05942 | | | 3 | SM00233 | | | 9 | 001-099 |
| 0223WG | 22 | GA | | | 10-9 | 33-25-12 | D05942 | | | 3 | SM00233 | | | 9 | 115-199 |
| 0224WO | 22 | GA | | | 11-1 | 33-25-12 | D05942 | | | 4 | SM00234 | | | 9 | 001-099 |
| 0224WO | 22 | GA | | | 10-9 | 33-25-12 | D05942 | | | 4 | SM00234 | | | 9 | 115-199 |
| 0225V | 22 | GA | | | 11-1 | 33-25-12 | D05942 | | | 5 | SM00235 | | | 9 | 001-099 |
| 0225V | 22 | GA | | | 10-9 | 33-25-12 | D05942 | | | 5 | SM00235 | | | 9 | 115-199 |
| 0226WN | 16 | GA | | | 11-1 | 33-23-12 | D05942 | | | 6 | SM00236 | | | 9 | 001-099 |
| 0226WN | 16 | GA | | | 10-9 | 33-23-12 | D05942 | | | 6 | SM00236 | | | 9 | 115-199 |
| 0227W | 20 | GA | | | 11-1 | 33-24-12 | D05942 | | | 7 | SM00237 | | | 9 | 001-099 |
| 0227W | 20 | GA | | | 10-9 | 33-24-12 | D05942 | | | 7 | SM00237 | | | 9 | 115-199 |
| 0228WP | 16 | GA | | | 11-1 | 33-23-12 | D05942 | | | 8 | SM00238 | | | 9 | 001-099 |
| 0228WP | 16 | GA | | | 10-9 | 33-23-12 | D05942 | | | 8 | SM00238 | | | 9 | 115-199 |
| 0229AJ | 20 | GA | | | 11-1 | 35-21-12 | D05942 | | | 11 | SM00239 | | | 9 | 001-099 |
| 0229AJ | 20 | GA | | | 10-9 | 35-21-12 | D05942 | | | 11 | SM00239 | | | 9 | 115-199 |
| 0230K | 18 | GA | | | 11-1 | 35-21-12 | D05942 | | | 10 | SM00240 | | | 9 | 001-099 |
| 0230K | 18 | GA | | | 10-9 | 35-21-12 | D05942 | | | 10 | SM00240 | | | 9 | 115-199 |
| 0231G | 16 | GA | | | 11-2 | 33-24-12 | D05944 | | | 1 | SM00231 | | | 9 | 001-099 |
| 0231G | 16 | GA | | | 10-10 | 33-24-12 | D05944 | | | 1 | SM00231 | | | 9 | 115-199 |
| 0232WV | 22 | GA | | | 11-2 | 33-25-12 | D05944 | | | 2 | SM00232 | | | 9 | 001-099 |
| 0232WV | 22 | GA | | | 10-10 | 33-25-12 | D05944 | | | 2 | SM00232 | | | 9 | 115-199 |
| 0233WG | 22 | GA | | | 11-2 | 33-25-12 | D05944 | | | 3 | SM00233 | | | 9 | 001-099 |
| 0233WG | 22 | GA | | | 10-10 | 33-25-12 | D05944 | | | 3 | SM00233 | | | 9 | 115-199 |
| 0234WO | 22 | GA | | | 11-2 | 33-25-12 | D05944 | | | 4 | SM00234 | | | 9 | 001-099 |
| 0234WO | 22 | GA | | | 10-10 | 33-25-12 | D05944 | | | 4 | SM00234 | | | 9 | 115-199 |
| 0235V | 22 | GA | | | 11-2 | 33-25-12 | D05944 | | | 5 | SM00235 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 11

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | | |
| 0235V | 22 | | GA | | 10-10 | 33-25-12 | D05944 | | 5 | | | SM00235 | | 9 | | 115-199 | |
| 0236WN | 16 | | GA | | 11-2 | 33-23-12 | D05944 | | 6 | | | SM00236 | | 9 | | 001-099 | |
| 0236WN | 16 | | GA | | 10-10 | 33-23-12 | D05944 | | 6 | | | SM00236 | | 9 | | 115-199 | |
| 0237W | 20 | | GA | | 11-2 | 33-24-12 | D05944 | | 7 | | | SM00237 | | 9 | | 001-099 | |
| 0237W | 20 | | GA | | 10-10 | 33-24-12 | D05944 | | 7 | | | SM00237 | | 9 | | 115-199 | |
| 0238WP | 16 | | GA | | 11-2 | 33-23-12 | D05944 | | 8 | | | SM00238 | | 9 | | 001-099 | |
| 0238WP | 16 | | GA | | 10-10 | 33-23-12 | D05944 | | 8 | | | SM00238 | | 9 | | 115-199 | |
| 0239AJ | 20 | | GA | | 11-2 | 35-21-12 | D05944 | | 11 | | | SM00239 | | 9 | | 001-099 | |
| 0239AJ | 20 | | GA | | 10-10 | 35-21-12 | D05944 | | 11 | | | SM00239 | | 9 | | 115-199 | |
| 0240K | 18 | | GA | | 11-2 | 35-21-12 | D05944 | | 10 | | | SM00240 | | 9 | | 001-099 | |
| 0240K | 18 | | GA | | 10-10 | 35-21-12 | D05944 | | 10 | | | SM00240 | | 9 | | 115-199 | |
| 0251G | 16 | | GA | | 9-2 | 33-24-12 | D05772 | | 1 | | | SM00251 | | 9 | | 001-099 | |
| 0251G | 16 | | GA | | 8-10 | 33-24-12 | D05772 | | 1 | | | SM00251 | | 9 | | 115-199 | |
| 0252WV | 22 | | GA | | 9-2 | 33-25-12 | D05772 | | 2 | | | SM00252 | | 9 | | 001-099 | |
| 0252WV | 22 | | GA | | 8-10 | 33-25-12 | D05772 | | 2 | | | SM00252 | | 9 | | 115-199 | |
| 0253WG | 22 | | GA | | 9-2 | 33-25-12 | D05772 | | 3 | | | SM00253 | | 9 | | 001-099 | |
| 0253WG | 22 | | GA | | 8-10 | 33-25-12 | D05772 | | 3 | | | SM00253 | | 9 | | 115-199 | |
| 0254WO | 22 | | GA | | 9-2 | 33-25-12 | D05772 | | 4 | | | SM00254 | | 9 | | 001-099 | |
| 0254WO | 22 | | GA | | 8-10 | 33-25-12 | D05772 | | 4 | | | SM00254 | | 9 | | 115-199 | |
| 0255V | 22 | | GA | | 9-2 | 33-25-12 | D05772 | | 5 | | | SM00255 | | 9 | | 001-099 | |
| 0255V | 22 | | GA | | 8-10 | 33-25-12 | D05772 | | 5 | | | SM00255 | | 9 | | 115-199 | |
| 0256WN | 16 | | GA | | 9-2 | 33-23-12 | D05772 | | 6 | | | SM00256 | | 9 | | 001-099 | |
| 0256WN | 16 | | GA | | 8-10 | 33-23-12 | D05772 | | 6 | | | SM00256 | | 9 | | 115-199 | |
| 0257W | 20 | | GA | | 9-2 | 33-24-12 | D05772 | | 7 | | | SM00257 | | 9 | | 001-099 | |
| 0257W | 20 | | GA | | 8-10 | 33-24-12 | D05772 | | 7 | | | SM00257 | | 9 | | 115-199 | |
| 0258WP | 16 | | GA | | 9-2 | 33-23-12 | D05772 | | 8 | | | SM00258 | | 9 | | 001-099 | |
| 0258WP | 16 | | GA | | 8-10 | 33-23-12 | D05772 | | 8 | | | SM00258 | | 9 | | 115-199 | |
| 0259AJ | 20 | | GA | | 9-2 | 35-21-12 | D05772 | | 11 | | | SM00259 | | 9 | | 001-099 | |
| 0259AJ | 20 | | GA | | 8-10 | 35-21-12 | D05772 | | 11 | | | SM00259 | | 9 | | 115-199 | |
| 0260K | 18 | | GA | | 9-2 | 35-21-12 | D05772 | | 10 | | | SM00260 | | 9 | | 001-099 | |
| 0260K | 18 | | GA | | 8-10 | 35-21-12 | D05772 | | 10 | | | SM00260 | | 9 | | 115-199 | |
| 0411G | 16 | | GA | | 2-11 | 33-24-12 | SM00011 | | | 9 | | SM00031 | | 9 | | 001-099 | |
| 0411G | 16 | | GA | | 2-3 | 33-24-12 | SM00011 | | | 9 | | SM00031 | | 9 | | 115-199 | |
| 0412WV | 22 | | GA | | 2-11 | 33-25-11 | SM00012 | | | 9 | | SM00032 | | 9 | | 001-099 | |
| 0412WV | 22 | | GA | | 2-3 | 33-25-11 | SM00012 | | | 9 | | SM00032 | | 9 | | 115-199 | |
| 0413WG | 22 | | GA | | 2-11 | 33-25-11 | SM00013 | | | 9 | | SM00033 | | 9 | | 001-099 | |
| 0413WG | 22 | | GA | | 2-3 | 33-25-11 | SM00013 | | | 9 | | SM00033 | | 9 | | 115-199 | |
| 0414WO | 22 | | GA | | 2-11 | 33-25-11 | SM00014 | | | 9 | | SM00034 | | 9 | | 001-099 | |
| 0414WO | 22 | | GA | | 2-3 | 33-25-11 | SM00014 | | | 9 | | SM00034 | | 9 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 12

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | |
| 0415V | 22 | | GA | | 2-11 | 33-25-11 | SM00015 | | | 9 | SM00035 | | | 9 | 001-099 |
| 0415V | 22 | | GA | | 2-3 | 33-25-11 | SM00015 | | | 9 | SM00035 | | | 9 | 115-199 |
| 0416WN | 16 | | GA | | 2-11 | 33-23-11 | SM00016 | | | 9 | SM00036 | | | 9 | 001-099 |
| 0416WN | 16 | | GA | | 2-3 | 33-23-11 | SM00016 | | | 9 | SM00036 | | | 9 | 115-199 |
| 0417W | 20 | | GA | | 2-11 | 33-24-12 | SM00017 | | | 9 | SM00037 | | | 9 | 001-099 |
| 0417W | 20 | | GA | | 2-3 | 33-24-12 | SM00017 | | | 9 | SM00037 | | | 9 | 115-199 |
| 0418WP | 16 | | GA | | 2-11 | 33-23-11 | SM00018 | | | 9 | SM00038 | | | 9 | 001-099 |
| 0418WP | 16 | | GA | | 2-3 | 33-23-11 | SM00018 | | | 9 | SM00038 | | | 9 | 115-199 |
| 0419AJ | 16 | | GA | | 2-11 | 35-21-12 | SM00019 | | | 9 | SM00039 | | | 9 | 001-099 |
| 0419AJ | 16 | | GA | | 2-3 | 35-21-12 | SM00019 | | | 9 | SM00039 | | | 9 | 115-199 |
| 0420K | 18 | | GA | | 2-11 | 35-21-12 | SM00020 | | | 9 | SM00040 | | | 9 | 001-099 |
| 0420K | 18 | | GA | | 2-3 | 35-21-12 | SM00020 | | | 9 | SM00040 | | | 9 | 115-199 |
| 0431G | 16 | | GA | | 2-9 | 33-24-12 | SM00031 | | | 9 | SM00051 | | | 9 | 001-099 |
| 0431G | 16 | | GA | | 2-1 | 33-24-12 | SM00031 | | | 9 | SM00051 | | | 9 | 115-199 |
| 0432WV | 22 | | GA | | 2-9 | 33-25-11 | SM00032 | | | 9 | SM00052 | | | 9 | 001-099 |
| 0432WV | 22 | | GA | | 2-1 | 33-25-11 | SM00032 | | | 9 | SM00052 | | | 9 | 115-199 |
| 0433WG | 22 | | GA | | 2-9 | 33-25-11 | SM00033 | | | 9 | SM00053 | | | 9 | 001-099 |
| 0433WG | 22 | | GA | | 2-1 | 33-25-11 | SM00033 | | | 9 | SM00053 | | | 9 | 115-199 |
| 0434WO | 22 | | GA | | 2-9 | 33-25-11 | SM00034 | | | 9 | SM00054 | | | 9 | 001-099 |
| 0434WO | 22 | | GA | | 2-1 | 33-25-11 | SM00034 | | | 9 | SM00054 | | | 9 | 115-199 |
| 0435V | 22 | | GA | | 2-9 | 33-25-11 | SM00035 | | | 9 | SM00055 | | | 9 | 001-099 |
| 0435V | 22 | | GA | | 2-1 | 33-25-11 | SM00035 | | | 9 | SM00055 | | | 9 | 115-199 |
| 0436WN | 16 | | GA | | 2-9 | 33-23-11 | SM00036 | | | 9 | SM00056 | | | 9 | 001-099 |
| 0436WN | 16 | | GA | | 2-1 | 33-23-11 | SM00036 | | | 9 | SM00056 | | | 9 | 115-199 |
| 0437W | 20 | | GA | | 2-9 | 33-24-12 | SM00037 | | | 9 | SM00057 | | | 9 | 001-099 |
| 0437W | 20 | | GA | | 2-1 | 33-24-12 | SM00037 | | | 9 | SM00057 | | | 9 | 115-199 |
| 0438WP | 16 | | GA | | 2-9 | 33-23-11 | SM00038 | | | 9 | SM00058 | | | 9 | 001-099 |
| 0438WP | 16 | | GA | | 2-1 | 33-23-11 | SM00038 | | | 9 | SM00058 | | | 9 | 115-199 |
| 0439AJ | 16 | | GA | | 2-9 | 35-21-12 | SM00039 | | | 9 | SM00059 | | | 9 | 001-099 |
| 0439AJ | 16 | | GA | | 2-1 | 35-21-12 | SM00039 | | | 9 | SM00059 | | | 9 | 115-199 |
| 0440K | 18 | | GA | | 2-9 | 35-21-12 | SM00040 | | | 9 | SM00060 | | | 9 | 001-099 |
| 0440K | 18 | | GA | | 2-1 | 35-21-12 | SM00040 | | | 9 | SM00060 | | | 9 | 115-199 |
| 0451G | 16 | | GA | | 4-6 | 33-24-12 | SM00051 | | | 9 | SM00071 | | | 9 | 001-099 |
| 0451G | 16 | | GA | | 3-10 | 33-24-12 | SM00051 | | | 9 | SM00071 | | | 9 | 115-199 |
| 0452WV | 22 | | GA | | 4-6 | 33-25-11 | SM00052 | | | 9 | SM00072 | | | 9 | 001-099 |
| 0452WV | 22 | | GA | | 3-10 | 33-25-11 | SM00052 | | | 9 | SM00072 | | | 9 | 115-199 |
| 0453WG | 22 | | GA | | 4-6 | 33-25-11 | SM00053 | | | 9 | SM00073 | | | 9 | 001-099 |
| 0453WG | 22 | | GA | | 3-10 | 33-25-11 | SM00053 | | | 9 | SM00073 | | | 9 | 115-199 |
| 0454WO | 22 | | GA | | 4-6 | 33-25-11 | SM00054 | | | 9 | SM00074 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 13

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|--|----------|---------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | | |
| 0454WO | 22 | GA | | 3-10 | 33-25-11 | | SM00054 | | | 9 | | SM00074 | | 9 | | 115-199 |
| 0455V | 22 | GA | | 4-6 | 33-25-11 | | SM00055 | | | 9 | | SM00075 | | 9 | | 001-099 |
| 0455V | 22 | GA | | 3-10 | 33-25-11 | | SM00055 | | | 9 | | SM00075 | | 9 | | 115-199 |
| 0456WN | 16 | GA | | 4-6 | 33-23-11 | | SM00056 | | | 9 | | SM00076 | | 9 | | 001-099 |
| 0456WN | 16 | GA | | 3-9 | 33-23-11 | | SM00056 | | | 9 | | SM00076 | | 9 | | 115-199 |
| 0457W | 20 | GA | | 4-6 | 33-24-12 | | SM00057 | | | 9 | | SM00077 | | 9 | | 001-099 |
| 0457W | 20 | GA | | 3-10 | 33-24-12 | | SM00057 | | | 9 | | SM00077 | | 9 | | 115-199 |
| 0458WP | 16 | GA | | 4-6 | 33-23-11 | | SM00058 | | | 9 | | SM00078 | | 9 | | 001-099 |
| 0458WP | 16 | GA | | 3-10 | 33-23-11 | | SM00058 | | | 9 | | SM00078 | | 9 | | 115-199 |
| 0459AJ | 16 | GA | | 4-6 | 35-21-12 | | SM00059 | | | 9 | | SM00079 | | 9 | | 001-099 |
| 0459AJ | 16 | GA | | 3-10 | 35-21-12 | | SM00059 | | | 9 | | SM00079 | | 9 | | 115-199 |
| 0460K | 18 | GA | | 4-6 | 35-21-12 | | SM00060 | | | 9 | | SM00080 | | 9 | | 001-099 |
| 0460K | 18 | GA | | 3-10 | 35-21-12 | | SM00060 | | | 9 | | SM00080 | | 9 | | 115-199 |
| 0471G | 16 | GA | | 4-5 | 33-24-12 | | SM00071 | | | 9 | | SM00091 | | 9 | | 001-099 |
| 0471G | 16 | GA | | 3-9 | 33-24-12 | | SM00071 | | | 9 | | SM00091 | | 9 | | 115-199 |
| 0472WV | 22 | GA | | 4-5 | 33-25-11 | | SM00072 | | | 9 | | SM00092 | | 9 | | 001-099 |
| 0472WV | 22 | GA | | 3-9 | 33-25-11 | | SM00072 | | | 9 | | SM00092 | | 9 | | 115-199 |
| 0473WG | 22 | GA | | 4-5 | 33-25-11 | | SM00073 | | | 9 | | SM00093 | | 9 | | 001-099 |
| 0473WG | 22 | GA | | 3-9 | 33-25-11 | | SM00073 | | | 9 | | SM00093 | | 9 | | 115-199 |
| 0474WO | 22 | GA | | 4-5 | 33-25-11 | | SM00074 | | | 9 | | SM00094 | | 9 | | 001-099 |
| 0474WO | 22 | GA | | 3-9 | 33-25-11 | | SM00074 | | | 9 | | SM00094 | | 9 | | 115-199 |
| 0475V | 22 | GA | | 4-5 | 33-25-11 | | SM00075 | | | 9 | | SM00095 | | 9 | | 001-099 |
| 0475V | 22 | GA | | 3-9 | 33-25-11 | | SM00075 | | | 9 | | SM00095 | | 9 | | 115-199 |
| 0476WN | 16 | GA | | 4-5 | 33-23-11 | | SM00076 | | | 9 | | SM00096 | | 9 | | 001-099 |
| 0476WN | 16 | GA | | 3-9 | 33-23-11 | | SM00076 | | | 9 | | SM00096 | | 9 | | 115-199 |
| 0477W | 20 | GA | | 4-5 | 33-24-12 | | SM00077 | | | 9 | | SM00097 | | 9 | | 001-099 |
| 0477W | 20 | GA | | 3-9 | 33-24-12 | | SM00077 | | | 9 | | SM00097 | | 9 | | 115-199 |
| 0478WP | 16 | GA | | 4-5 | 33-23-11 | | SM00078 | | | 9 | | SM00098 | | 9 | | 001-099 |
| 0478WP | 16 | GA | | 3-9 | 33-23-11 | | SM00078 | | | 9 | | SM00098 | | 9 | | 115-199 |
| 0479AJ | 16 | GA | | 4-5 | 35-21-12 | | SM00079 | | | 9 | | SM00099 | | 9 | | 001-099 |
| 0479AJ | 16 | GA | | 3-9 | 35-21-12 | | SM00079 | | | 9 | | SM00099 | | 9 | | 115-199 |
| 0480K | 18 | GA | | 4-5 | 35-21-12 | | SM00080 | | | 9 | | SM00100 | | 9 | | 001-099 |
| 0480K | 18 | GA | | 3-9 | 35-21-12 | | SM00080 | | | 9 | | SM00100 | | 9 | | 115-199 |
| 0491G | 16 | GA | | 6-7 | 33-24-12 | | SM00091 | | | 9 | | SM00111 | | 9 | | 001-099 |
| 0491G | 16 | GA | | 5-5 | 33-24-12 | | SM00091 | | | 9 | | SM00111 | | 9 | | 115-199 |
| 0492WV | 22 | GA | | 6-7 | 33-25-11 | | SM00092 | | | 9 | | SM00112 | | 9 | | 001-099 |
| 0492WV | 22 | GA | | 5-5 | 33-25-11 | | SM00092 | | | 9 | | SM00112 | | 9 | | 115-199 |
| 0493WG | 22 | GA | | 6-7 | 33-25-11 | | SM00093 | | | 9 | | SM00113 | | 9 | | 001-099 |
| 0493WG | 22 | GA | | 5-5 | 33-25-11 | | SM00093 | | | 9 | | SM00113 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 14

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|--|----|--|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0494WO | 22 | | GA | 6-7 | 33-25-11 | SM00094 | | | | 9 | SM00114 | | | 9 | 001-099 |
| 0494WO | 22 | | GA | 5-5 | 33-25-11 | SM00094 | | | | 9 | SM00114 | | | 9 | 115-199 |
| 0495V | 22 | | GA | 6-7 | 33-25-11 | SM00095 | | | | 9 | SM00115 | | | 9 | 001-099 |
| 0495V | 22 | | GA | 5-5 | 33-25-11 | SM00095 | | | | 9 | SM00115 | | | 9 | 115-199 |
| 0496WN | 16 | | GA | 6-7 | 33-23-11 | SM00096 | | | | 9 | SM00116 | | | 9 | 001-099 |
| 0496WN | 16 | | GA | 5-5 | 33-23-11 | SM00096 | | | | 9 | SM00116 | | | 9 | 115-199 |
| 0497W | 20 | | GA | 6-7 | 33-24-12 | SM00097 | | | | 9 | SM00117 | | | 9 | 001-099 |
| 0497W | 20 | | GA | 5-5 | 33-24-12 | SM00097 | | | | 9 | SM00117 | | | 9 | 115-199 |
| 0498WP | 16 | | GA | 6-7 | 33-23-11 | SM00098 | | | | 9 | SM00118 | | | 9 | 001-099 |
| 0498WP | 16 | | GA | 5-5 | 33-23-11 | SM00098 | | | | 9 | SM00118 | | | 9 | 115-199 |
| 0499AJ | 16 | | GA | 6-7 | 35-21-12 | SM00099 | | | | 9 | SM00119 | | | 9 | 001-099 |
| 0499AJ | 16 | | GA | 5-5 | 35-21-12 | SM00099 | | | | 9 | SM00119 | | | 9 | 115-199 |
| 0500K | 18 | | GA | 6-7 | 35-21-12 | SM00100 | | | | 9 | SM00120 | | | 9 | 001-099 |
| 0500K | 18 | | GA | 5-5 | 35-21-12 | SM00100 | | | | 9 | SM00120 | | | 9 | 115-199 |
| 0511G | 16 | | GA | 4-6 | 33-24-12 | SM00111 | | | | 9 | SM00131 | | | 9 | 001-099 |
| 0511G | 16 | | GA | 3-10 | 33-24-12 | SM00111 | | | | 9 | SM00131 | | | 9 | 115-199 |
| 0512WV | 22 | | GA | 4-6 | 33-25-11 | SM00112 | | | | 9 | SM00132 | | | 9 | 001-099 |
| 0512WV | 22 | | GA | 3-10 | 33-25-11 | SM00112 | | | | 9 | SM00132 | | | 9 | 115-199 |
| 0513WG | 22 | | GA | 4-6 | 33-25-11 | SM00113 | | | | 9 | SM00133 | | | 9 | 001-099 |
| 0513WG | 22 | | GA | 3-10 | 33-25-11 | SM00113 | | | | 9 | SM00133 | | | 9 | 115-199 |
| 0514WO | 22 | | GA | 4-6 | 33-25-11 | SM00114 | | | | 9 | SM00134 | | | 9 | 001-099 |
| 0514WO | 22 | | GA | 3-10 | 33-25-11 | SM00114 | | | | 9 | SM00134 | | | 9 | 115-199 |
| 0515V | 22 | | GA | 4-6 | 33-25-11 | SM00115 | | | | 9 | SM00135 | | | 9 | 001-099 |
| 0515V | 22 | | GA | 3-10 | 33-25-11 | SM00115 | | | | 9 | SM00135 | | | 9 | 115-199 |
| 0516WN | 16 | | GA | 4-6 | 33-23-11 | SM00116 | | | | 9 | SM00136 | | | 9 | 001-099 |
| 0516WN | 16 | | GA | 3-10 | 33-23-11 | SM00116 | | | | 9 | SM00136 | | | 9 | 115-199 |
| 0517W | 20 | | GA | 4-6 | 33-24-12 | SM00117 | | | | 9 | SM00137 | | | 9 | 001-099 |
| 0517W | 20 | | GA | 3-10 | 33-24-12 | SM00117 | | | | 9 | SM00137 | | | 9 | 115-199 |
| 0518WP | 16 | | GA | 4-6 | 33-23-11 | SM00118 | | | | 9 | SM00138 | | | 9 | 001-099 |
| 0518WP | 16 | | GA | 3-10 | 33-23-11 | SM00118 | | | | 9 | SM00138 | | | 9 | 115-199 |
| 0519AJ | 16 | | GA | 4-6 | 35-21-12 | SM00119 | | | | 9 | SM00139 | | | 9 | 001-099 |
| 0519AJ | 16 | | GA | 3-10 | 35-21-12 | SM00119 | | | | 9 | SM00139 | | | 9 | 115-199 |
| 0520K | 18 | | GA | 4-6 | 35-21-12 | SM00120 | | | | 9 | SM00140 | | | 9 | 001-099 |
| 0520K | 18 | | GA | 3-10 | 35-21-12 | SM00120 | | | | 9 | SM00140 | | | 9 | 115-199 |
| 0531G | 16 | | GA | 9-9 | 33-24-12 | SM00131 | | | | 9 | SM00171 | | | 9 | 001-099 |
| 0531G | 16 | | GA | 9-1 | 33-24-12 | SM00131 | | | | 9 | SM00171 | | | 9 | 115-199 |
| 0532WV | 22 | | GA | 9-9 | 33-25-11 | SM00132 | | | | 9 | SM00172 | | | 9 | 001-099 |
| 0532WV | 22 | | GA | 9-1 | 33-25-11 | SM00132 | | | | 9 | SM00172 | | | 9 | 115-199 |
| 0533WG | 22 | | GA | 9-9 | 33-25-11 | SM00133 | | | | 9 | SM00173 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 15

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0533WG | 22 | | GA | | 9-1 | 33-25-11 | | SM00133 | | | | SM00173 | | | 9 | 115-199 |
| 0534WO | 22 | | GA | | 9-9 | 33-25-11 | | SM00134 | | | | SM00174 | | | 9 | 001-099 |
| 0534WO | 22 | | GA | | 9-1 | 33-25-11 | | SM00134 | | | | SM00174 | | | 9 | 115-199 |
| 0535V | 22 | | GA | | 9-9 | 33-25-11 | | SM00135 | | | | SM00175 | | | 9 | 001-099 |
| 0535V | 22 | | GA | | 9-1 | 33-25-11 | | SM00135 | | | | SM00175 | | | 9 | 115-199 |
| 0537W | 20 | | GA | | 9-9 | 33-24-12 | | SM00137 | | | | SM00177 | | | 9 | 001-099 |
| 0537W | 20 | | GA | | 9-1 | 33-24-12 | | SM00137 | | | | SM00177 | | | 9 | 115-199 |
| 0538WP | 16 | | GA | | 9-9 | 33-23-11 | | SM00138 | | | | SM00178 | | | 9 | 001-099 |
| 0538WP | 16 | | GA | | 9-1 | 33-23-11 | | SM00138 | | | | SM00178 | | | 9 | 115-199 |
| 0539AJ | 16 | | GA | | 9-9 | 35-21-12 | | SM00139 | | | | SM00179 | | | 9 | 001-099 |
| 0539AJ | 16 | | GA | | 9-1 | 35-21-12 | | SM00139 | | | | SM00179 | | | 9 | 115-199 |
| 0540K | 18 | | GA | | 9-9 | 35-21-12 | | SM00140 | | | | SM00180 | | | 9 | 001-099 |
| 0540K | 18 | | GA | | 9-1 | 35-21-12 | | SM00140 | | | | SM00180 | | | 9 | 115-199 |
| 0571G | 16 | | GA | | 5-3 | 33-24-12 | | SM00171 | | | | SM00191 | | | 9 | 001-099 |
| 0571G | 16 | | GA | | 4-7 | 33-24-12 | | SM00171 | | | | SM00191 | | | 9 | 115-199 |
| 0572WV | 22 | | GA | | 5-3 | 33-25-11 | | SM00172 | | | | SM00192 | | | 9 | 001-099 |
| 0572WV | 22 | | GA | | 4-7 | 33-25-12 | | SM00172 | | | | SM00192 | | | 9 | 115-199 |
| 0573WG | 22 | | GA | | 5-3 | 33-25-11 | | SM00173 | | | | SM00193 | | | 9 | 001-099 |
| 0573WG | 22 | | GA | | 4-7 | 33-25-12 | | SM00173 | | | | SM00193 | | | 9 | 115-199 |
| 0574WO | 22 | | GA | | 5-3 | 33-25-11 | | SM00174 | | | | SM00194 | | | 9 | 001-099 |
| 0574WO | 22 | | GA | | 4-7 | 33-25-12 | | SM00174 | | | | SM00194 | | | 9 | 115-199 |
| 0575V | 22 | | GA | | 5-3 | 33-25-11 | | SM00175 | | | | SM00195 | | | 9 | 001-099 |
| 0575V | 22 | | GA | | 4-7 | 33-25-12 | | SM00175 | | | | SM00195 | | | 9 | 115-199 |
| 0576WN | 16 | | GA | | 5-3 | 33-23-12 | | SM00176 | | | | SM00196 | | | 9 | 001-099 |
| 0576WN | 16 | | GA | | 4-7 | 33-23-12 | | SM00176 | | | | SM00196 | | | 9 | 115-199 |
| 0577W | 20 | | GA | | 5-3 | 33-24-12 | | SM00177 | | | | SM00197 | | | 9 | 001-099 |
| 0577W | 20 | | GA | | 4-7 | 33-24-12 | | SM00177 | | | | SM00197 | | | 9 | 115-199 |
| 0578WP | 16 | | GA | | 5-3 | 33-23-12 | | SM00178 | | | | SM00198 | | | 9 | 001-099 |
| 0578WP | 16 | | GA | | 4-7 | 33-23-12 | | SM00178 | | | | SM00198 | | | 9 | 115-199 |
| 0579AJ | 16 | | GA | | 5-3 | 35-21-12 | | SM00179 | | | | SM00199 | | | 9 | 001-099 |
| 0579AJ | 16 | | GA | | 4-7 | 35-21-12 | | SM00179 | | | | SM00199 | | | 9 | 115-199 |
| 0580K | 18 | | GA | | 5-3 | 35-21-12 | | SM00180 | | | | SM00200 | | | 9 | 001-099 |
| 0580K | 18 | | GA | | 4-7 | 35-21-12 | | SM00180 | | | | SM00200 | | | 9 | 115-199 |
| 0591G | 16 | | GA | | 2-11 | 33-24-12 | | SM00191 | | | | SM00211 | | | 9 | 001-099 |
| 0591G | 16 | | GA | | 2-2 | 33-24-12 | | SM00191 | | | | SM00211 | | | 9 | 115-199 |
| 0592WV | 22 | | GA | | 2-11 | 33-25-12 | | SM00192 | | | | SM00212 | | | 9 | 001-099 |
| 0592WV | 22 | | GA | | 2-2 | 33-25-12 | | SM00192 | | | | SM00212 | | | 9 | 115-199 |
| 0593WG | 22 | | GA | | 2-11 | 33-25-12 | | SM00193 | | | | SM00213 | | | 9 | 001-099 |
| 0593WG | 22 | | GA | | 2-2 | 33-25-12 | | SM00193 | | | | SM00213 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 16

May 17/2006



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|------|---------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | | |
| 0633WG | 22 | | GA | | 6-3 | 33-25-12 | SM00233 | | | 9 | | | SM00253 | | 9 | 115-199 | |
| 0634WO | 22 | | GA | | 7-0 | 33-25-12 | SM00234 | | | 9 | | | SM00254 | | 9 | 001-099 | |
| 0634WO | 22 | | GA | | 6-3 | 33-25-12 | SM00234 | | | 9 | | | SM00254 | | 9 | 115-199 | |
| 0635V | 22 | | GA | | 7-0 | 33-25-12 | SM00235 | | | 9 | | | SM00255 | | 9 | 001-099 | |
| 0635V | 22 | | GA | | 6-3 | 33-25-12 | SM00235 | | | 9 | | | SM00255 | | 9 | 115-199 | |
| 0636WN | 16 | | GA | | 7-0 | 33-23-12 | SM00236 | | | 9 | | | SM00256 | | 9 | 001-099 | |
| 0636WN | 16 | | GA | | 6-3 | 33-23-12 | SM00236 | | | 9 | | | SM00256 | | 9 | 115-199 | |
| 0637W | 20 | | GA | | 7-0 | 33-24-12 | SM00237 | | | 9 | | | SM00257 | | 9 | 001-099 | |
| 0637W | 20 | | GA | | 6-3 | 33-24-12 | SM00237 | | | 9 | | | SM00257 | | 9 | 115-199 | |
| 0638WP | 16 | | GA | | 7-0 | 33-23-12 | SM00238 | | | 9 | | | SM00258 | | 9 | 001-099 | |
| 0638WP | 16 | | GA | | 6-3 | 33-23-12 | SM00238 | | | 9 | | | SM00258 | | 9 | 115-199 | |
| 0639AJ | 16 | | GA | | 7-0 | 35-21-12 | SM00239 | | | 9 | | | SM00259 | | 9 | 001-099 | |
| 0639AJ | 16 | | GA | | 6-3 | 35-21-12 | SM00239 | | | 9 | | | SM00259 | | 9 | 115-199 | |
| 0640K | 18 | | GA | | 7-0 | 35-21-12 | SM00240 | | | 9 | | | SM00260 | | 9 | 001-099 | |
| 0640K | 18 | | GA | | 6-3 | 35-21-12 | SM00240 | | | 9 | | | SM00260 | | 9 | 115-199 | |
| 0701 | 16 | | GA | | 11-8 | 33-24-12 | D41548J | | 1 | | | | SM00031 | | 9 | 001-099 | |
| 0701 | 16 | | GA | | 11-5 | 33-24-12 | D41548J | | 1 | | | | SM00031 | | 9 | 115-199 | |
| 0702 | 22 | | GA | | 11-8 | 33-25-11 | D41548J | | 2 | | | | SM00032 | | 9 | 001-099 | |
| 0702 | 22 | | GA | | 11-5 | 33-25-11 | D41548J | | 2 | | | | SM00032 | | 9 | 115-199 | |
| 0703 | 22 | | GA | | 11-8 | 33-25-11 | D41548J | | 3 | | | | SM00033 | | 9 | 001-099 | |
| 0703 | 22 | | GA | | 11-5 | 33-25-11 | D41548J | | 3 | | | | SM00033 | | 9 | 115-199 | |
| 0704 | 22 | | GA | | 11-8 | 33-25-11 | D41548J | | 4 | | | | SM00034 | | 9 | 001-099 | |
| 0704 | 22 | | GA | | 11-5 | 33-25-11 | D41548J | | 4 | | | | SM00034 | | 9 | 115-199 | |
| 0705 | 22 | | GA | | 11-8 | 33-25-11 | D41548J | | 5 | | | | SM00035 | | 9 | 001-099 | |
| 0705 | 22 | | GA | | 11-5 | 33-25-11 | D41548J | | 5 | | | | SM00035 | | 9 | 115-199 | |
| 0706 | 16 | | GA | | 11-8 | 33-23-11 | D41548J | | 6 | | | | SM00036 | | 9 | 001-099 | |
| 0706 | 16 | | GA | | 11-5 | 33-23-11 | D41548J | | 6 | | | | SM00036 | | 9 | 115-199 | |
| 0707 | 20 | | GA | | 11-8 | 33-24-12 | D41548J | | 7 | | | | SM00037 | | 9 | 001-099 | |
| 0707 | 20 | | GA | | 11-5 | 33-24-12 | D41548J | | 7 | | | | SM00037 | | 9 | 115-199 | |
| 0708 | 16 | | GA | | 11-8 | 33-23-11 | D41548J | | 8 | | | | SM00038 | | 9 | 001-099 | |
| 0708 | 16 | | GA | | 11-5 | 33-23-11 | D41548J | | 8 | | | | SM00038 | | 9 | 115-199 | |
| 0709 | 20 | | GA | | 11-8 | 35-21-12 | D41548J | | 11 | | | | SM00039 | | 9 | 001-099 | |
| 0709 | 20 | | GA | | 11-5 | 35-21-12 | D41548J | | 11 | | | | SM00039 | | 9 | 115-199 | |
| 0710 | 18 | | GA | | 11-8 | 35-21-12 | D41548J | | 10 | | | | SM00040 | | 9 | 001-099 | |
| 0710 | 18 | | GA | | 11-5 | 35-21-12 | D41548J | | 10 | | | | SM00040 | | 9 | 115-199 | |
| 0711 | 22 | | GA | | 11-5 | 33-25-11 | D41548J | | 9 | | | | SM06039 | | 9 | 115-199 | |
| 0740 | 18 | | GA | | 5-4 | 35-21-12 | D41498J | | 10 | | | | SM00140 | | 9 | 009-099 | |
| 0741 | 16 | | GA | | 5-4 | 33-24-12 | D41498J | | 1 | | | | SM00131 | | 9 | 009-099 | |
| 0742 | 22 | | GA | | 5-4 | 33-25-11 | D41498J | | 2 | | | | SM00132 | | 9 | 009-099 | |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 18

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0745 | 22 | GA | | | 5-4 | 33-25-11 | D41498J | 5 | | | SM00135 | | 9 | | 009-099 |
| 0747 | 20 | GA | | | 5-4 | 33-24-12 | D41498J | 7 | | | SM00137 | | 9 | | 009-099 |
| 0749 | 20 | GA | | | 5-4 | 35-21-12 | D41498J | 11 | | | SM00139 | | 9 | | 009-099 |
| 0800 | 22 | GA | | | 66-11 | 23-31-41 | D40310P | 3 | | | D40312J | 12 | | | 001-099 |
| 0800 | 22 | GA | | | 66-8 | 23-31-41 | D40310P | 3 | | | D40312J | 12 | | | 115-199 |
| 0801 | 16 | GA | | | 29-10 | 33-24-12 | D40310P | 1 | | | SM00071 | | 9 | | 001-099 |
| 0801 | 16 | GA | | | 29-6 | 33-24-12 | D40310P | 1 | | | SM00071 | | 9 | | 115-199 |
| 0802 | 22 | GA | | | 29-10 | 33-25-11 | D40310P | 2 | | | SM00072 | | 9 | | 001-099 |
| 0805 | 22 | GA | | | 29-10 | 33-25-11 | D40310P | 5 | | | SM00075 | | 9 | | 001-099 |
| 0805 | 22 | GA | | | 29-6 | 33-25-11 | D40310P | 5 | | | SM00075 | | 9 | | 115-199 |
| 0807 | 20 | GA | | | 29-10 | 33-24-12 | D40310P | 7 | | | SM00077 | | 9 | | 001-099 |
| 0807 | 20 | GA | | | 29-6 | 33-24-12 | D40310P | 7 | | | SM00077 | | 9 | | 115-199 |
| 0809 | 16 | GA | | | 29-10 | 35-21-12 | D40310P | 39 | | | SM00079 | | 9 | | 001-099 |
| 0809 | 16 | GA | | | 29-6 | 35-21-12 | D40310P | 39 | | | SM00079 | | 9 | | 115-199 |
| 0811 | 16 | GA | | | 4-2 | 33-24-12 | SM00251 | | 9 | | D40312J | | 1 | | 001-099 |
| 0811 | 16 | GA | | | 3-7 | 33-24-12 | SM00251 | | 9 | | D40312J | | 1 | | 115-199 |
| 0812 | 22 | GA | | | 4-2 | 33-25-12 | SM00252 | | 9 | | D40312J | | 2 | | 001-099 |
| 0812 | 22 | GA | | | 3-7 | 33-25-12 | SM00252 | | 9 | | D40312J | | 2 | | 115-199 |
| 0813 | 22 | GA | | | 4-2 | 33-25-12 | SM00253 | | 9 | | D40312J | | 3 | | 001-099 |
| 0813 | 22 | GA | | | 3-7 | 33-25-12 | SM00253 | | 9 | | D40312J | | 3 | | 115-199 |
| 0814 | 22 | GA | | | 4-2 | 33-25-12 | SM00254 | | 9 | | D40312J | | 4 | | 001-099 |
| 0814 | 22 | GA | | | 3-7 | 33-25-12 | SM00254 | | 9 | | D40312J | | 4 | | 115-199 |
| 0815 | 22 | GA | | | 4-2 | 33-25-12 | SM00255 | | 9 | | D40312J | | 5 | | 001-099 |
| 0815 | 22 | GA | | | 3-7 | 33-25-12 | SM00255 | | 9 | | D40312J | | 5 | | 115-199 |
| 0817 | 20 | GA | | | 4-2 | 33-24-12 | SM00257 | | 9 | | D40312J | | 7 | | 001-099 |
| 0817 | 20 | GA | | | 3-7 | 33-24-12 | SM00257 | | 9 | | D40312J | | 7 | | 115-199 |
| 0822 | 16 | GA | | | 66-11 | SPARE | D40310P | 22 | | | D40312J | | 22 | | 001-099 |
| 0822 | 16 | GA | | | 66-8 | SPARE | D40310P | 22 | | | D40312J | | 22 | | 115-199 |
| 0825 | 22 | GA | | | 36-0 | 23-31-41 | D40310P | 25 | | | D01231 | | 3 | | ALL |
| 0826 | 22 | GA | | | 66-11 | 23-31-41 | D40310P | 26 | | | D40312J | | 26 | | 001-099 |
| 0826 | 22 | GA | | | 66-8 | 23-31-41 | D40310P | 26 | | | D40312J | | 26 | | 115-199 |
| 0829 | 16 | GA | | | 66-11 | 35-21-13 | D40310P | 29 | | | D40312J | | 29 | | 001-099 |
| 0829 | 16 | GA | | | 66-8 | 35-21-13 | D40310P | 29 | | | D40312J | | 29 | | 115-199 |
| 0833 | 20 | GA | | | 66-11 | 33-23-13 | D40310P | 33 | | | D40312J | | 33 | | 001-099 |
| 0833 | 20 | GA | | | 66-8 | 33-23-13 | D40310P | 33 | | | D40312J | | 33 | | 115-199 |
| 0834 | 20 | GA | | | 66-11 | 33-23-14 | D40310P | 34 | | | D40312J | | 34 | | 001-099 |
| 0834 | 20 | GA | | | 66-8 | 33-23-14 | D40310P | 34 | | | D40312J | | 34 | | 115-199 |
| 0835 | 22 | GA | | | 66-11 | 33-25-13 | D40310P | 35 | | | D40312J | | 35 | | 001-099 |
| 0835 | 22 | GA | | | 66-8 | 33-25-13 | D40310P | 35 | | | D40312J | | 35 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 19

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|-------|-----|--|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | | |
| 0836 | 16 | GA | | 4-2 | 33-23-12 | D40312J | 36 | | | | | SM00256 | | 9 | | 001-099 |
| 0836 | 16 | GA | | 3-7 | 33-23-12 | D40312J | 36 | | | | | SM00256 | | 9 | | 115-199 |
| 0838 | 16 | GA | | 4-2 | 33-23-12 | D40312J | 38 | | | | | SM00258 | | 9 | | 001-099 |
| 0838 | 16 | GA | | 3-7 | 33-23-12 | D40312J | 38 | | | | | SM00258 | | 9 | | 115-199 |
| 0839 | 16 | GA | | 4-2 | 35-21-12 | SM00259 | | 9 | | | | D40312J | 39 | | | 001-099 |
| 0839 | 16 | GA | | 3-7 | 35-21-12 | SM00259 | | 9 | | | | D40312J | 39 | | | 115-199 |
| 0840 | 18 | GA | | 4-2 | 35-21-12 | SM00260 | | 9 | | | | D40312J | 40 | | | 001-099 |
| 0840 | 18 | GA | | 3-7 | 35-21-12 | SM00260 | | 9 | | | | D40312J | 40 | | | 115-199 |
| 0845 | 22 | GA | | 49-11 | 23-31-41 | D40310P | | 15 | | | | D01247 | 3 | | | ALL |
| 0850 | 14 | GA | | 7-3 | 33-23-11 | T10051 | | GND | E | | | GD03217 | AC.. | E | | ALL |
| 0851 | 20 | GA | | 32-4 | 33-23-11 | D40310P | | 31 | | | | T10051 | HV3 | E | | ALL |
| 0856 | 16 | GA | | 5-4 | 33-23-11 | T10051 | | LV | E | | | SM00056 | | 9 | | 001-099 |
| 0856 | 16 | GA | | 4-11 | 33-23-11 | T10051 | | LV | E | | | SM00056 | | 9 | | 115-199 |
| 0861 | 14 | GA | | 6-6 | 33-23-12 | T10012 | | GND | E | | | GD03227 | AC.. | E | | 001-099 |
| 0861 | 14 | GA | | 6-8 | 33-23-12 | T10012 | | GND | E | | | GD03227 | AC.. | E | | 115-199 |
| 0862 | 20 | GA | | 60-3 | 33-23-12 | D40310P | | 32 | | | | T10012 | HV3 | E | | ALL |
| 0866 | 16 | GA | | 7-0 | 33-23-12 | T10012 | | LV | E | | | SM00216 | | 9 | | 001-099 |
| 0866 | 16 | GA | | 6-8 | 33-23-12 | T10012 | | LV | E | | | SM00216 | | 9 | | 115-199 |
| 0876 | 20 | GA | | 10-4 | 35-21-12 | SM00219 | | | 9 | | | SP01166 | | 9 | | 115-199 |
| 0877 | 18 | GA | | 3-9 | 35-21-12 | SP01164 | | | 9 | | | GD02402 | DC.. | E | | 115-199 |
| 0881 | 20 | GA | | 11-2 | 35-21-12 | D04338 | | 1 | VY | | | SM00019 | | 9 | | 001-099 |
| 0881 | 20 | GA | | 10-10 | 35-21-12 | D04338 | | 1 | VY | | | SM00019 | | 9 | | 115-199 |
| 0891 | 18 | GA | | 2-8 | 35-21-12 | D04340 | | 1 | VG | | | GD01553 | DC.. | E | | ALL |
| 0903 | 16 | GA | | 13-6 | 33-24-12 | D41288J | | 1 | VY | | | SM00171 | | 9 | | 001-099 |
| 0903 | 16 | GA | | 11-1 | 33-24-12 | D06316 | | 1 | | | | SM00171 | | 9 | | 115-199 |
| 0904 | 20 | GA | | 13-5 | 33-24-12 | D41284J | | 1 | VS | | | SM00177 | | 9 | | 001-099 |
| 0904 | 20 | GA | | 11-1 | 33-24-12 | D06316 | | 7 | | | | SM00177 | | 9 | | 115-199 |
| 0905 | 16 | GA | | 10-0 | 33-24-12 | D41286P | | 1 | VG | | | GD03221 | AC.. | E | | 001-099 |
| 0905 | 16 | GA | | 7-11 | 33-24-12 | D06316 | | 8 | | | | GD03221 | AC.. | E | | 115-199 |
| 0906 | 16 | GA | | 8-9 | 33-24-12 | D41296J | | 1 | VY | | | SM00191 | | 9 | | 001-099 |
| 0907 | 20 | GA | | 8-9 | 33-24-12 | D41292J | | 1 | VS | | | SM00197 | | 9 | | 001-099 |
| 0908 | 16 | GA | | 3-5 | 33-23-11 | SM00018 | | | 9 | | | GD03209 | AC.. | E | | 001-099 |
| 0908 | 16 | GA | | 2-11 | 33-23-11 | SM00018 | | | 9 | | | GD03209 | AC.. | E | | 115-199 |
| 0909 | 16 | GA | | 4-11 | 33-24-12 | D41294P | | 1 | VG | | | GD03656 | AC.. | E | | 001-099 |
| 0910 | 18 | GA | | 3-3 | 35-21-12 | SM00020 | | | 9 | | | GD03207 | DC.. | E | | 001-099 |
| 0910 | 18 | GA | | 3-1 | 35-21-12 | SM00020 | | | 9 | | | GD03207 | DC.. | E | | 115-199 |
| 0911 | 20 | GA | | 66-11 | SPARE | D40310P | | 11 | | | | D40312J | 11 | | | 001-099 |
| 0911 | 20 | GA | | 66-8 | SPARE | D40310P | | 11 | | | | D40312J | 10 | | | 115-199 |
| 0912 | 16 | GA | | 4-11 | 33-24-12 | SM00191 | | | 9 | | | SP01562 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 20

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|-------|------|------|-------------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 0913 | 20 | GA | | | 4-11 | 33-24-12 | SM00197 | | | 9 | SP01560 | | | 9 | 115-199 |
| 0918 | 16 | GA | | | 6-11 | 33-23-11 | SM00118 | | | 9 | GD03225 | AC.. | E | | 001-099 |
| 0918 | 16 | GA | | | 6-8 | 33-23-11 | SM00118 | | | 9 | GD03225 | AC.. | E | | 115-199 |
| 0919 | 22 | GA | | | 3-7 | 33-25-12 | SM06259 | | | 9 | D40312J | 11 | | | 115-199 |
| 0920 | 18 | GA | | | 6-3 | 35-21-12 | SM00120 | | | 9 | GD03213 | DC.. | E | | 001-099 |
| 0920 | 18 | GA | | | 5-5 | 35-21-12 | SM00120 | | | 9 | GD03213 | DC.. | E | | 115-199 |
| 0921 | 16 | GA | | | 2-3 | 33-23-11 | SM00078 | | | 9 | GD03219 | AC.. | E | | 001-099 |
| 0921 | 16 | GA | | | 1-11 | 33-23-11 | SM00078 | | | 9 | GD03219 | AC.. | E | | 115-199 |
| 0922 | 16 | GA | | | 6-3 | 33-23-11 | SM00138 | | | 9 | GD03221 | AC.. | E | | 001-099 |
| 0922 | 16 | GA | | | 5-5 | 33-23-11 | SM00138 | | | 9 | GD03221 | AC.. | E | | 115-199 |
| 0923 | 16 | GA | | | 1-11 | 33-23-12 | SM00238 | | | 9 | GD03223 | AC.. | E | | 001-099 |
| 0923 | 16 | GA | | | 1-8 | 33-23-12 | SM00238 | | | 9 | GD03223 | AC.. | E | | 115-199 |
| 0928 | 16 | GA | | | 6-0 | 33-23-12 | SM00198 | | | 9 | GD01257 | AC.. | E | | 001-099 |
| 0928 | 16 | GA | | | 4-8 | 33-23-12 | SM00198 | | | 9 | GD01257 | AC.. | E | | 115-199 |
| 0930 | 18 | GA | | | 6-1 | 35-21-12 | SM00200 | | | 9 | GD01259 | DC.. | E | | 001-099 |
| 0930 | 18 | GA | | | 4-7 | 35-21-12 | SM00200 | | | 9 | GD01259 | DC.. | E | | 115-199 |
| 0938 | 22 | GA | | | 13-7 | 33-25-11 | SM00134 | | | 9 | SP00538 | | | 9 | 001-099 |
| 0942 | 22 | GA | | | 13-7 | 33-25-11 | SM00133 | | | 9 | SP00542 | | | 9 | 001-099 |
| 0942 | 22 | GA | | | 10-9 | 33-25-12 | SM00193 | | | 9 | SP00542 | | | 9 | 115-199 |
| 0952 | 22 | GA | | | 7-7 | 33-25-11 | SM00014 | | | 9 | SP00552 | | | 9 | 001-099 |
| 0952 | 22 | GA | | | 6-10 | SPARE | SM00014 | | | 9 | SP00552 | | | 9 | 115-199 |
| 0962 | 22 | GA | | | 27-10 | 33-25-11 | SM06039 | | | 9 | SP01120 | | | 9 | 115-199 |
| 0963 | 22 | GA | | | 4-2 | 33-25-12 | SM06179 | | | 9 | SP01126 | | | 9 | 115-199 |
| 0964 | 22 | GA | | | 4-2 | 33-25-12 | SM00172 | | | 9 | SP01128 | | | 9 | 115-199 |
| 0965 | 22 | GA | | | 6-8 | 33-25-12 | SM00174 | | | 9 | SP01124 | | | 9 | 115-199 |
| 0966 | 22 | GA | | | 23-11 | 33-25-12 | D40312J | 19 | | | SP01122 | | | 9 | 115-199 |
| 0974 | 20 | GA | | | 6-3 | 23-31-21 | D01231 | | | 4 | SM00040 | | | 9 | 001-099 |
| 0974 | 20 | GA | | | 6-0 | 23-31-21 | D01231 | | | 4 | SM00040 | | | 9 | 115-199 |
| 0984 | 20 | GA | | | 4-11 | 23-31-21 | D01247 | | | 4 | SM00180 | | | 9 | 001-099 |
| 0984 | 20 | GA | | | 4-8 | 23-31-21 | D01247 | | | 4 | SM00180 | | | 9 | 115-199 |
| 0985 | 16 | GA | | | 4-2 | 33-23-12 | SM00258 | | | 9 | GD03239 | AC.. | E | | 001-099 |
| 0985 | 16 | GA | | | 4-4 | 33-23-12 | SM00258 | | | 9 | GD03239 | AC.. | E | | 115-199 |
| 2001B | 22 | GB | ZA | | 5-4 | 23-31-21 | D41498J | 14 | | | SM00144 | | | 9 | 009-099 |
| 2001R | 22 | GB | ZA | | 0-0 | 23-31-21 | D41498J | 13 | | | SM00143 | | | 9 | 009-099 |
| 2011B | 22 | GB | AO | | 10-11 | 23-31-21 | D05902 | | | 14 | SM00024 | | | 9 | 001-099 |
| 2011B | 22 | GB | AO | | 10-7 | 23-31-21 | D05902 | | | 13 | SM00023 | | | 9 | 115-199 |
| 2011R | 22 | GB | AO | | 0-0 | 23-31-21 | D05902 | | | 13 | SM00023 | | | 9 | 001-099 |
| 2011R | 22 | GB | AO | | 0-0 | 23-31-21 | D05902 | | | 14 | SM00024 | | | 9 | 115-199 |
| 2021B | 22 | GB | B | | 10-7 | 23-31-21 | D05904 | | | 14 | SM00024 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 21

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | |
| 2021B | 22 | | GB | B | 10-3 | 23-31-21 | D05904 | 13 | | | SM00023 | | 9 | | 115-199 |
| 2021R | 22 | | GB | B | 0-0 | 23-31-21 | D05904 | 13 | | | SM00023 | | 9 | | 001-099 |
| 2021R | 22 | | GB | B | 0-0 | 23-31-21 | D05904 | 14 | | | SM00024 | | 9 | | 115-199 |
| 2023B | 22 | | GB | AM | 2-11 | 23-31-21 | SM00024 | | 9 | | SM00044 | | 9 | | 001-099 |
| 2023B | 22 | | GB | AM | 2-3 | 23-31-21 | SM00023 | | 9 | | SM00043 | | 9 | | 115-199 |
| 2023R | 22 | | GB | AM | 0-0 | 23-31-21 | SM00023 | | 9 | | SM00043 | | 9 | | 001-099 |
| 2023R | 22 | | GB | AM | 0-0 | 23-31-21 | SM00024 | | 9 | | SM00044 | | 9 | | 115-199 |
| 2031B | 22 | | GB | C | 7-10 | 23-31-21 | D05906 | 14 | | | SM00044 | | 9 | | 001-099 |
| 2031B | 22 | | GB | C | 7-7 | 23-31-21 | D05906 | 13 | | | SM00043 | | 9 | | 115-199 |
| 2031R | 22 | | GB | C | 0-0 | 23-31-21 | D05906 | 13 | | | SM00043 | | 9 | | 001-099 |
| 2031R | 22 | | GB | C | 0-0 | 23-31-21 | D05906 | 14 | | | SM00044 | | 9 | | 115-199 |
| 2043B | 22 | | GB | Y | 2-9 | 23-31-21 | SM00044 | | 9 | | SM00064 | | 9 | | 001-099 |
| 2043B | 22 | | GB | Y | 2-1 | 23-31-21 | SM00043 | | 9 | | SM00063 | | 9 | | 115-199 |
| 2043R | 22 | | GB | Y | 0-0 | 23-31-21 | SM00043 | | 9 | | SM00063 | | 9 | | 001-099 |
| 2043R | 22 | | GB | Y | 0-0 | 23-31-21 | SM00044 | | 9 | | SM00064 | | 9 | | 115-199 |
| 2051B | 22 | | GB | E | 7-0 | 23-31-21 | D05908 | 14 | | | SM00064 | | 9 | | 001-099 |
| 2051B | 22 | | GB | E | 6-9 | 23-31-21 | D05908 | 13 | | | SM00063 | | 9 | | 115-199 |
| 2051R | 22 | | GB | E | 0-0 | 23-31-21 | D05908 | 13 | | | SM00063 | | 9 | | 001-099 |
| 2051R | 22 | | GB | E | 0-0 | 23-31-21 | D05908 | 14 | | | SM00064 | | 9 | | 115-199 |
| 2061B | 22 | | GB | F | 7-0 | 23-31-21 | D05910 | 14 | | | SM00064 | | 9 | | 001-099 |
| 2061B | 22 | | GB | F | 6-8 | 23-31-21 | D05910 | 13 | | | SM00063 | | 9 | | 115-199 |
| 2061R | 22 | | GB | F | 0-0 | 23-31-21 | D05910 | 13 | | | SM00063 | | 9 | | 001-099 |
| 2061R | 22 | | GB | F | 0-0 | 23-31-21 | D05910 | 14 | | | SM00064 | | 9 | | 115-199 |
| 2063B | 22 | | GB | AA | 4-6 | 23-31-21 | SM00064 | | 9 | | SM00084 | | 9 | | 001-099 |
| 2063B | 22 | | GB | AA | 3-10 | 23-31-21 | SM00063 | | 9 | | SM00083 | | 9 | | 115-199 |
| 2063R | 22 | | GB | AA | 0-0 | 23-31-21 | SM00063 | | 9 | | SM00083 | | 9 | | 001-099 |
| 2063R | 22 | | GB | AA | 0-0 | 23-31-21 | SM00064 | | 9 | | SM00084 | | 9 | | 115-199 |
| 2071B | 22 | | GB | G | 8-6 | 23-31-21 | D05912 | 14 | | | SM00084 | | 9 | | 001-099 |
| 2071B | 22 | | GB | G | 7-0 | 23-31-21 | D05912 | 13 | | | SM00083 | | 9 | | 115-199 |
| 2071R | 22 | | GB | G | 0-0 | 23-31-21 | D05912 | 13 | | | SM00083 | | 9 | | 001-099 |
| 2071R | 22 | | GB | G | 0-0 | 23-31-21 | D05912 | 14 | | | SM00084 | | 9 | | 115-199 |
| 2081B | 22 | | GB | H | 9-3 | 23-31-21 | D05914 | 14 | | | SM00084 | | 9 | | 001-099 |
| 2081B | 22 | | GB | H | 8-11 | 23-31-21 | D05914 | 13 | | | SM00083 | | 9 | | 115-199 |
| 2081R | 22 | | GB | H | 0-0 | 23-31-21 | D05914 | 13 | | | SM00083 | | 9 | | 001-099 |
| 2081R | 22 | | GB | H | 0-0 | 23-31-21 | D05914 | 14 | | | SM00084 | | 9 | | 115-199 |
| 2083B | 22 | | GB | AB | 4-5 | 23-31-21 | SM00084 | | 9 | | SM00104 | | 9 | | 001-099 |
| 2083B | 22 | | GB | AB | 3-9 | 23-31-21 | SM00083 | | 9 | | SM00103 | | 9 | | 115-199 |
| 2083R | 22 | | GB | AB | 0-0 | 23-31-21 | SM00083 | | 9 | | SM00103 | | 9 | | 001-099 |
| 2083R | 22 | | GB | AB | 0-0 | 23-31-21 | SM00084 | | 9 | | SM00104 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 22

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|--------|---------|------|-------------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | | |
| 2091B | 22 | GB | I | | 7-7 | 23-31-21 | D05916 | | 14 | | | SM00104 | | 9 | | 001-099 |
| 2091B | 22 | GB | I | | 7-4 | 23-31-21 | D05916 | | 13 | | | SM00103 | | 9 | | 115-199 |
| 2091R | 22 | GB | I | | 0-0 | 23-31-21 | D05916 | | 13 | | | SM00103 | | 9 | | 001-099 |
| 2091R | 22 | GB | I | | 0-0 | 23-31-21 | D05916 | | 14 | | | SM00104 | | 9 | | 115-199 |
| 2101B | 22 | GB | J | | 8-10 | 23-31-21 | D05918 | | 14 | | | SM00104 | | 9 | | 001-099 |
| 2101B | 22 | GB | J | | 8-7 | 23-31-21 | D05918 | | 13 | | | SM00103 | | 9 | | 115-199 |
| 2101R | 22 | GB | J | | 0-0 | 23-31-21 | D05918 | | 13 | | | SM00103 | | 9 | | 001-099 |
| 2101R | 22 | GB | J | | 0-0 | 23-31-21 | D05918 | | 14 | | | SM00104 | | 9 | | 115-199 |
| 2103B | 22 | GB | AC | | 6-7 | 23-31-21 | SM00104 | | | 9 | | SM00124 | | 9 | | 001-099 |
| 2103B | 22 | GB | AC | | 5-5 | 23-31-21 | SM00103 | | | 9 | | SM00123 | | 9 | | 115-199 |
| 2103R | 22 | GB | AC | | 0-0 | 23-31-21 | SM00103 | | | 9 | | SM00123 | | 9 | | 001-099 |
| 2103R | 22 | GB | AC | | 0-0 | 23-31-21 | SM00104 | | | 9 | | SM00124 | | 9 | | 115-199 |
| 2111B | 22 | GB | K | | 8-9 | 23-31-21 | D05920 | | 14 | | | SM00124 | | 9 | | 001-099 |
| 2111B | 22 | GB | K | | 8-5 | 23-31-21 | D05920 | | 13 | | | SM00123 | | 9 | | 115-199 |
| 2111R | 22 | GB | K | | 0-0 | 23-31-21 | D05920 | | 13 | | | SM00123 | | 9 | | 001-099 |
| 2111R | 22 | GB | K | | 0-0 | 23-31-21 | D05920 | | 14 | | | SM00124 | | 9 | | 115-199 |
| 2121B | 22 | GB | L | | 7-6 | 23-31-21 | D05922 | | 14 | | | SM00124 | | 9 | | 001-099 |
| 2121B | 22 | GB | L | | 7-1 | 23-31-21 | D05922 | | 13 | | | SM00123 | | 9 | | 115-199 |
| 2121R | 22 | GB | L | | 0-0 | 23-31-21 | D05922 | | 13 | | | SM00123 | | 9 | | 001-099 |
| 2121R | 22 | GB | L | | 0-0 | 23-31-21 | D05922 | | 14 | | | SM00124 | | 9 | | 115-199 |
| 2123B | 22 | GB | AD | | 4-6 | 23-31-21 | SM00124 | | | 9 | | SM00144 | | 9 | | 001-099 |
| 2123B | 22 | GB | AD | | 3-10 | 23-31-21 | SM00123 | | | 9 | | SM00143 | | 9 | | 115-199 |
| 2123R | 22 | GB | AD | | 0-0 | 23-31-21 | SM00123 | | | 9 | | SM00143 | | 9 | | 001-099 |
| 2123R | 22 | GB | AD | | 0-0 | 23-31-21 | SM00124 | | | 9 | | SM00144 | | 9 | | 115-199 |
| 2131B | 22 | GB | M | | 9-11 | 23-31-21 | D05924 | | 14 | | | SM00144 | | 9 | | 001-099 |
| 2131B | 22 | GB | M | | 9-7 | 23-31-21 | D05924 | | 13 | | | SM00143 | | 9 | | 115-199 |
| 2131R | 22 | GB | M | | 0-0 | 23-31-21 | D05924 | | 13 | | | SM00143 | | 9 | | 001-099 |
| 2131R | 22 | GB | M | | 0-0 | 23-31-21 | D05924 | | 14 | | | SM00144 | | 9 | | 115-199 |
| 2141B | 22 | GB | N | | 7-11 | 23-31-21 | D05926 | | 14 | | | SM00144 | | 9 | | 001-099 |
| 2141B | 22 | GB | N | | 7-7 | 23-31-21 | D05926 | | 13 | | | SM00143 | | 9 | | 115-199 |
| 2141R | 22 | GB | N | | 0-0 | 23-31-21 | D05926 | | 13 | | | SM00143 | | 9 | | 001-099 |
| 2141R | 22 | GB | N | | 0-0 | 23-31-21 | D05926 | | 14 | | | SM00144 | | 9 | | 115-199 |
| 2143B | 22 | GB | AF | | 9-9 | 23-31-21 | SM00144 | | | 9 | | SM00184 | | 9 | | 001-099 |
| 2143B | 22 | GB | AF | | 9-1 | 23-31-21 | SM00143 | | | 9 | | SM00183 | | 9 | | 115-199 |
| 2143R | 22 | GB | AF | | 0-0 | 23-31-21 | SM00143 | | | 9 | | SM00183 | | 9 | | 001-099 |
| 2143R | 22 | GB | AF | | 0-0 | 23-31-21 | SM00144 | | | 9 | | SM00184 | | 9 | | 115-199 |
| 2151B | 22 | GB | AE | | 9-0 | 23-31-21 | D05928 | | 14 | | | SM00144 | | 9 | | 001-099 |
| 2151B | 22 | GB | AE | | 8-4 | 23-31-21 | D05928 | | 13 | | | SM00143 | | 9 | | 115-199 |
| 2151R | 22 | GB | AE | | 0-0 | 23-31-21 | D05928 | | 13 | | | SM00143 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 23

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3702 | 286N3702 | | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | | |
| 2151R | 22 | GB | AE | | 0-0 | 23-31-21 | D05928 | | 14 | | | SM00144 | | 9 | | 115-199 | |
| 2161B | 22 | GB | O | | 3-6 | 23-31-21 | D05930 | | 14 | | | SM00184 | | 9 | | 001-099 | |
| 2161B | 22 | GB | O | | 3-3 | 23-31-21 | D05930 | | 13 | | | SM00183 | | 9 | | 115-199 | |
| 2161R | 22 | GB | O | | 0-0 | 23-31-21 | D05930 | | 13 | | | SM00183 | | 9 | | 001-099 | |
| 2161R | 22 | GB | O | | 0-0 | 23-31-21 | D05930 | | 14 | | | SM00184 | | 9 | | 115-199 | |
| 2171B | 22 | GB | P | | 3-6 | 23-31-21 | D05932 | | 14 | | | SM00184 | | 9 | | 001-099 | |
| 2171B | 22 | GB | P | | 3-2 | 23-31-21 | D05932 | | 13 | | | SM00183 | | 9 | | 115-199 | |
| 2171R | 22 | GB | P | | 0-0 | 23-31-21 | D05932 | | 13 | | | SM00183 | | 9 | | 001-099 | |
| 2171R | 22 | GB | P | | 0-0 | 23-31-21 | D05932 | | 14 | | | SM00184 | | 9 | | 115-199 | |
| 2181B | 22 | GB | Q | | 9-1 | 23-31-22 | D05934 | | 14 | | | SM00204 | | 9 | | 001-099 | |
| 2181B | 22 | GB | Q | | 8-9 | 23-31-22 | D05934 | | 13 | | | SM00203 | | 9 | | 115-199 | |
| 2181R | 22 | GB | Q | | 0-0 | 23-31-22 | D05934 | | 13 | | | SM00203 | | 9 | | 001-099 | |
| 2181R | 22 | GB | Q | | 0-0 | 23-31-22 | D05934 | | 14 | | | SM00204 | | 9 | | 115-199 | |
| 2183B | 22 | GB | AH | | 5-3 | 23-31-22 | SM00184 | | | 9 | | SM00204 | | 9 | | 001-099 | |
| 2183B | 22 | GB | AH | | 4-7 | 23-31-22 | SM00183 | | | 9 | | SM00203 | | 9 | | 115-199 | |
| 2183R | 22 | GB | AH | | 0-0 | 23-31-22 | SM00183 | | | 9 | | SM00203 | | 9 | | 001-099 | |
| 2183R | 22 | GB | AH | | 0-0 | 23-31-22 | SM00184 | | | 9 | | SM00204 | | 9 | | 115-199 | |
| 2191B | 22 | GB | R | | 8-1 | 23-31-22 | D05936 | | 14 | | | SM00204 | | 9 | | 001-099 | |
| 2191B | 22 | GB | R | | 7-9 | 23-31-22 | D05936 | | 13 | | | SM00203 | | 9 | | 115-199 | |
| 2191R | 22 | GB | R | | 0-0 | 23-31-22 | D05936 | | 13 | | | SM00203 | | 9 | | 001-099 | |
| 2191R | 22 | GB | R | | 0-0 | 23-31-22 | D05936 | | 14 | | | SM00204 | | 9 | | 115-199 | |
| 2201B | 22 | GB | AJ | | 8-4 | 23-31-22 | D05938 | | 14 | | | SM00224 | | 9 | | 001-099 | |
| 2201B | 22 | GB | AJ | | 7-11 | 23-31-22 | D05938 | | 13 | | | SM00223 | | 9 | | 115-199 | |
| 2201R | 22 | GB | AJ | | 0-0 | 23-31-22 | D05938 | | 13 | | | SM00223 | | 9 | | 001-099 | |
| 2201R | 22 | GB | AJ | | 0-0 | 23-31-22 | D05938 | | 14 | | | SM00224 | | 9 | | 115-199 | |
| 2203B | 22 | GB | AK | | 2-11 | 23-31-22 | SM00204 | | | 9 | | SM00224 | | 9 | | 001-099 | |
| 2203B | 22 | GB | AK | | 2-2 | 23-31-22 | SM00203 | | | 9 | | SM00223 | | 9 | | 115-199 | |
| 2203R | 22 | GB | AK | | 0-0 | 23-31-22 | SM00203 | | | 9 | | SM00223 | | 9 | | 001-099 | |
| 2203R | 22 | GB | AK | | 0-0 | 23-31-22 | SM00204 | | | 9 | | SM00224 | | 9 | | 115-199 | |
| 2211B | 22 | GB | S | | 9-2 | 23-31-22 | D05940 | | 14 | | | SM00224 | | 9 | | 001-099 | |
| 2211B | 22 | GB | S | | 8-10 | 23-31-22 | D05940 | | 13 | | | SM00223 | | 9 | | 115-199 | |
| 2211R | 22 | GB | S | | 0-0 | 23-31-22 | D05940 | | 13 | | | SM00223 | | 9 | | 001-099 | |
| 2211R | 22 | GB | S | | 0-0 | 23-31-22 | D05940 | | 14 | | | SM00224 | | 9 | | 115-199 | |
| 2221B | 22 | GB | T | | 11-1 | 23-31-22 | D05942 | | 14 | | | SM00244 | | 9 | | 001-099 | |
| 2221B | 22 | GB | T | | 10-9 | 23-31-22 | D05942 | | 13 | | | SM00243 | | 9 | | 115-199 | |
| 2221R | 22 | GB | T | | 0-0 | 23-31-22 | D05942 | | 13 | | | SM00243 | | 9 | | 001-099 | |
| 2221R | 22 | GB | T | | 0-0 | 23-31-22 | D05942 | | 14 | | | SM00244 | | 9 | | 115-199 | |
| 2223B | 22 | GB | AL | | 4-4 | 23-31-22 | SM00224 | | | 9 | | SM00244 | | 9 | | 001-099 | |
| 2223B | 22 | GB | AL | | 3-9 | 23-31-22 | SM00223 | | | 9 | | SM00243 | | 9 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 24

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|-------|------|------|-------------|---------|-------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 2223R | 22 | GB | AL | | 0-0 | 23-31-22 | SM00223 | | | 9 | | SM00243 | | 9 | 001-099 |
| 2223R | 22 | GB | AL | | 0-0 | 23-31-22 | SM00224 | | | 9 | | SM00244 | | 9 | 115-199 |
| 2231B | 22 | GB | U | | 11-2 | 23-31-22 | D05944 | | 14 | | | SM00244 | | 9 | 001-099 |
| 2231B | 22 | GB | U | | 10-10 | 23-31-22 | D05944 | | 13 | | | SM00243 | | 9 | 115-199 |
| 2231R | 22 | GB | U | | 0-0 | 23-31-22 | D05944 | | 13 | | | SM00243 | | 9 | 001-099 |
| 2231R | 22 | GB | U | | 0-0 | 23-31-22 | D05944 | | 14 | | | SM00244 | | 9 | 115-199 |
| 2243B | 22 | GB | AP | | 7-0 | 23-31-22 | SM00244 | | | 9 | | SM00264 | | 9 | 001-099 |
| 2243B | 22 | GB | AP | | 6-3 | 23-31-22 | SM00243 | | | 9 | | SM00263 | | 9 | 115-199 |
| 2243R | 22 | GB | AP | | 0-0 | 23-31-22 | SM00243 | | | 9 | | SM00263 | | 9 | 001-099 |
| 2243R | 22 | GB | AP | | 0-0 | 23-31-22 | SM00244 | | | 9 | | SM00264 | | 9 | 115-199 |
| 2251B | 22 | GB | AQ | | 9-2 | 23-31-22 | D05772 | | 14 | | | SM00264 | | 9 | 001-099 |
| 2251B | 22 | GB | AQ | | 8-10 | 23-31-22 | D05772 | | 13 | | | SM00263 | | 9 | 115-199 |
| 2251R | 22 | GB | AQ | | 0-0 | 23-31-22 | D05772 | | 13 | | | SM00263 | | 9 | 001-099 |
| 2251R | 22 | GB | AQ | | 0-0 | 23-31-22 | D05772 | | 14 | | | SM00264 | | 9 | 115-199 |
| 2291B | 22 | GB | AG | | 4-11 | 23-31-21 | D01247 | | 1 | | | SM00184 | | 9 | 001-099 |
| 2291B | 22 | GB | AG | | 4-8 | 23-31-21 | D01247 | | 1 | | | SM00183 | | 9 | 115-199 |
| 2291R | 22 | GB | AG | | 0-0 | 23-31-21 | D01247 | | 2 | | | SM00183 | | 9 | 001-099 |
| 2291R | 22 | GB | AG | | 0-0 | 23-31-21 | D01247 | | 2 | | | SM00184 | | 9 | 115-199 |
| 2301B | 22 | GB | AN | | 11-8 | 23-31-21 | D41548J | | 14 | | | SM00044 | | 9 | 001-099 |
| 2301B | 22 | GB | AN | | 11-5 | 23-31-21 | D41548J | | 13 | | | SM00043 | | 9 | 115-199 |
| 2301R | 22 | GB | AN | | 0-0 | 23-31-21 | D41548J | | 13 | | | SM00043 | | 9 | 001-099 |
| 2301R | 22 | GB | AN | | 0-0 | 23-31-21 | D41548J | | 14 | | | SM00044 | | 9 | 115-199 |
| 2413B | 22 | GB | Z | | 29-10 | 23-31-21 | D40310P | | 13 | | | SM00084 | | 9 | 001-099 |
| 2413B | 22 | GB | Z | | 29-6 | 23-31-21 | D40310P | | 13 | | | SM00083 | | 9 | 115-199 |
| 2413R | 22 | GB | Z | | 0-0 | 23-31-21 | D40310P | | 14 | | | SM00083 | | 9 | 001-099 |
| 2413R | 22 | GB | Z | | 0-0 | 23-31-21 | D40310P | | 14 | | | SM00084 | | 9 | 115-199 |
| 2423B | 22 | GB | W | | 4-2 | 23-31-22 | D40312J | | 14 | | | SM00264 | | 9 | 001-099 |
| 2423B | 22 | GB | W | | 3-7 | 23-31-22 | D40312J | | 13 | | | SM00263 | | 9 | 115-199 |
| 2423R | 22 | GB | W | | 0-0 | 23-31-22 | D40312J | | 13 | | | SM00263 | | 9 | 001-099 |
| 2423R | 22 | GB | W | | 0-0 | 23-31-22 | D40312J | | 14 | | | SM00264 | | 9 | 115-199 |
| 2471B | 22 | GB | X | | 6-3 | 23-31-21 | D01231 | | 1 | | | SM00044 | | 9 | 001-099 |
| 2471B | 22 | GB | X | | 6-0 | 23-31-21 | D01231 | | 1 | | | SM00043 | | 9 | 115-199 |
| 2471R | 22 | GB | X | | 0-0 | 23-31-21 | D01231 | | 2 | | | SM00043 | | 9 | 001-099 |
| 2471R | 22 | GB | X | | 0-0 | 23-31-21 | D01231 | | 2 | | | SM00044 | | 9 | 115-199 |
| 6019AD | 22 | GA | | | 10-7 | 33-25-11 | D05902 | | 9 | | | SM06019 | | 9 | 115-199 |
| 6029AD | 22 | GA | | | 10-3 | 33-25-11 | D05904 | | 9 | | | SM06019 | | 9 | 115-199 |
| 6039AD | 22 | GA | | | 7-7 | 33-25-11 | D05906 | | 9 | | | SM06039 | | 9 | 115-199 |
| 6059AD | 22 | GA | | | 6-9 | 33-25-11 | D05908 | | 9 | | | SM06059 | | 9 | 115-199 |
| 6069AD | 22 | GA | | | 6-8 | 33-25-11 | D05910 | | 9 | | | SM06059 | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 25

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | |
|------------------------|-------------|-------|-----|--|----------|---------|------|------|--------|-------|---------|------|-------------|--------|---------|
| | GA | CO TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | |
| W3702 | 286N3702 | | | P36 TO PSU HARNESS-LEFT, FORWARD (continued) | | | | | | | | | | | |
| 6079AD | 22 | GA | | 7-0 | 33-25-11 | D05912 | | 9 | | | SM06079 | | 9 | | 115-199 |
| 6089AD | 22 | GA | | 8-11 | 33-25-11 | D05914 | | 9 | | | SM06079 | | 9 | | 115-199 |
| 6099AD | 22 | GA | | 7-4 | 33-25-11 | D05916 | | 9 | | | SM06099 | | 9 | | 115-199 |
| 6109AD | 22 | GA | | 8-7 | 33-25-11 | D05918 | | 9 | | | SM06099 | | 9 | | 115-199 |
| 6119AD | 22 | GA | | 8-5 | 33-25-11 | D05920 | | 9 | | | SM06119 | | 9 | | 115-199 |
| 6129AD | 22 | GA | | 7-1 | 33-25-11 | D05922 | | 9 | | | SM06119 | | 9 | | 115-199 |
| 6139AD | 22 | GA | | 9-7 | 33-25-11 | D05924 | | 9 | | | SM06139 | | 9 | | 115-199 |
| 6149AD | 22 | GA | | 7-7 | 33-25-11 | D05926 | | 9 | | | SM06139 | | 9 | | 115-199 |
| 6159AD | 22 | GA | | 8-4 | 33-25-11 | D05928 | | 9 | | | SM06139 | | 9 | | 115-199 |
| 6169AD | 22 | GA | | 3-3 | 33-25-11 | D05930 | | 9 | | | SM06179 | | 9 | | 115-199 |
| 6179AD | 22 | GA | | 3-2 | 33-25-11 | D05932 | | 9 | | | SM06179 | | 9 | | 115-199 |
| 6189AD | 22 | GA | | 8-9 | 33-25-12 | D05934 | | 9 | | | SM06199 | | 9 | | 115-199 |
| 6199AD | 22 | GA | | 7-9 | 33-25-12 | D05936 | | 9 | | | SM06199 | | 9 | | 115-199 |
| 6209AD | 22 | GA | | 7-11 | 33-25-12 | D05938 | | 9 | | | SM06219 | | 9 | | 115-199 |
| 6219AD | 22 | GA | | 8-10 | 33-25-12 | D05940 | | 9 | | | SM06219 | | 9 | | 115-199 |
| 6229AD | 22 | GA | | 10-9 | 33-25-12 | D05942 | | 9 | | | SM06239 | | 9 | | 115-199 |
| 6239AD | 22 | GA | | 10-10 | 33-25-12 | D05944 | | 9 | | | SM06239 | | 9 | | 115-199 |
| 6259AD | 22 | GA | | 8-10 | 33-25-12 | D05772 | | 9 | | | SM06259 | | 9 | | 115-199 |
| 6519AD | 22 | GA | | 2-3 | 33-25-11 | SM06019 | | | 9 | | SM06039 | | 9 | | 115-199 |
| 6539AD | 22 | GA | | 2-1 | 33-25-11 | SM06039 | | | 9 | | SM06059 | | 9 | | 115-199 |
| 6559AD | 22 | GA | | 3-10 | 33-25-11 | SM06059 | | | 9 | | SM06079 | | 9 | | 115-199 |
| 6579AD | 22 | GA | | 3-9 | 33-25-11 | SM06079 | | | 9 | | SM06099 | | 9 | | 115-199 |
| 6599AD | 22 | GA | | 5-5 | 33-25-11 | SM06099 | | | 9 | | SM06119 | | 9 | | 115-199 |
| 6619AD | 22 | GA | | 3-10 | 33-25-11 | SM06119 | | | 9 | | SM06139 | | 9 | | 115-199 |
| 6639AD | 22 | GA | | 9-1 | 33-25-11 | SM06139 | | | 9 | | SM06179 | | 9 | | 115-199 |
| 6679AD | 22 | GA | | 4-7 | 33-25-12 | SM06179 | | | 9 | | SM06199 | | 9 | | 115-199 |
| 6699AD | 22 | GA | | 2-2 | 33-25-12 | SM06199 | | | 9 | | SM06219 | | 9 | | 115-199 |
| 6719AD | 22 | GA | | 3-9 | 33-25-12 | SM06219 | | | 9 | | SM06239 | | 9 | | 115-199 |
| 6739AD | 22 | GA | | 6-3 | 33-25-12 | SM06239 | | | 9 | | SM06259 | | 9 | | 115-199 |
| W3704 | 286N3704 | | | PSU HARNESS-LEFT, CENTER | | | | | | | | | | | |
| 0011G | 16 | GA | | 7-3 | 33-24-13 | D05946 | | 1 | | | SM00011 | | 9 | | 001-099 |
| 0011G | 16 | GA | | 4-11 | 33-24-13 | D05946 | | 1 | | | SM00011 | | 9 | | 115-199 |
| 0012WV | 22 | GA | | 7-3 | 33-25-12 | D05946 | | 2 | | | SM00012 | | 9 | | 001-099 |
| 0012WV | 22 | GA | | 4-11 | 33-25-12 | D05946 | | 2 | | | SM00012 | | 9 | | 115-199 |
| 0013WG | 22 | GA | | 7-3 | 33-25-12 | D05946 | | 3 | | | SM00013 | | 9 | | 001-099 |
| 0013WG | 22 | GA | | 4-11 | 33-25-12 | D05946 | | 3 | | | SM00013 | | 9 | | 115-199 |
| 0014WO | 22 | GA | | 7-3 | 33-25-12 | D05946 | | 4 | | | SM00014 | | 9 | | 001-099 |
| 0014WO | 22 | GA | | 4-11 | 33-25-12 | D05946 | | 4 | | | SM00014 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 26

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|---------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W3704 | 286N3704 | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | |
| 0015V | 22 | | GA | 7-3 | 33-25-12 | D05946 | | | 5 | | SM00015 | | 9 | 001-099 | |
| 0015V | 22 | | GA | 4-11 | 33-25-12 | D05946 | | | 5 | | SM00015 | | 9 | 115-199 | |
| 0016WN | 16 | | GA | 7-3 | 33-23-12 | D05946 | | | 6 | | SM00016 | | 9 | 001-099 | |
| 0016WN | 16 | | GA | 4-11 | 33-23-12 | D05946 | | | 6 | | SM00016 | | 9 | 115-199 | |
| 0017W | 20 | | GA | 7-3 | 33-24-13 | D05946 | | | 7 | | SM00017 | | 9 | 001-099 | |
| 0017W | 20 | | GA | 4-11 | 33-24-13 | D05946 | | | 7 | | SM00017 | | 9 | 115-199 | |
| 0018WP | 16 | | GA | 7-3 | 33-23-12 | D05946 | | | 8 | | SM00018 | | 9 | 001-099 | |
| 0018WP | 16 | | GA | 4-11 | 33-23-12 | D05946 | | | 8 | | SM00018 | | 9 | 115-199 | |
| 0019AJ | 20 | | GA | 7-3 | 35-21-12 | D05946 | | | 11 | | SM00019 | | 9 | 001-099 | |
| 0019AJ | 20 | | GA | 4-11 | 35-21-12 | D05946 | | | 11 | | SM00019 | | 9 | 115-199 | |
| 0020K | 18 | | GA | 7-3 | 35-21-12 | D05946 | | | 10 | | SM00020 | | 9 | 001-099 | |
| 0020K | 18 | | GA | 4-11 | 35-21-12 | D05946 | | | 10 | | SM00020 | | 9 | 115-199 | |
| 0021G | 16 | | GA | 10-5 | 33-24-13 | D05948 | | | 1 | | SM00011 | | 9 | 001-099 | |
| 0021G | 16 | | GA | 10-0 | 33-24-13 | D05948 | | | 1 | | SM00011 | | 9 | 115-199 | |
| 0022WV | 22 | | GA | 10-5 | 33-25-12 | D05948 | | | 2 | | SM00012 | | 9 | 001-099 | |
| 0022WV | 22 | | GA | 10-0 | 33-25-12 | D05948 | | | 2 | | SM00012 | | 9 | 115-199 | |
| 0023WG | 22 | | GA | 10-5 | 33-25-12 | D05948 | | | 3 | | SM00013 | | 9 | 001-099 | |
| 0023WG | 22 | | GA | 10-0 | 33-25-12 | D05948 | | | 3 | | SM00013 | | 9 | 115-199 | |
| 0024WO | 22 | | GA | 10-5 | 33-25-12 | D05948 | | | 4 | | SM00014 | | 9 | 001-099 | |
| 0024WO | 22 | | GA | 10-0 | 33-25-12 | D05948 | | | 4 | | SM00014 | | 9 | 115-199 | |
| 0025V | 22 | | GA | 10-5 | 33-25-12 | D05948 | | | 5 | | SM00015 | | 9 | 001-099 | |
| 0025V | 22 | | GA | 10-0 | 33-25-12 | D05948 | | | 5 | | SM00015 | | 9 | 115-199 | |
| 0026WN | 16 | | GA | 10-5 | 33-23-12 | D05948 | | | 6 | | SM00016 | | 9 | 001-099 | |
| 0026WN | 16 | | GA | 10-0 | 33-23-12 | D05948 | | | 6 | | SM00016 | | 9 | 115-199 | |
| 0027W | 20 | | GA | 10-5 | 33-24-13 | D05948 | | | 7 | | SM00017 | | 9 | 001-099 | |
| 0027W | 20 | | GA | 10-0 | 33-24-13 | D05948 | | | 7 | | SM00017 | | 9 | 115-199 | |
| 0028WP | 16 | | GA | 10-5 | 33-23-12 | D05948 | | | 8 | | SM00018 | | 9 | 001-099 | |
| 0028WP | 16 | | GA | 10-0 | 33-23-12 | D05948 | | | 8 | | SM00018 | | 9 | 115-199 | |
| 0029AJ | 20 | | GA | 10-5 | 35-21-12 | D05948 | | | 11 | | SM00019 | | 9 | 001-099 | |
| 0029AJ | 20 | | GA | 10-0 | 35-21-12 | D05948 | | | 11 | | SM00019 | | 9 | 115-199 | |
| 0030K | 18 | | GA | 10-5 | 35-21-12 | D05948 | | | 10 | | SM00020 | | 9 | 001-099 | |
| 0030K | 18 | | GA | 10-0 | 35-21-12 | D05948 | | | 10 | | SM00020 | | 9 | 115-199 | |
| 0031G | 16 | | GA | 8-7 | 33-24-13 | D05950 | | | 1 | | SM00031 | | 9 | ALL | |
| 0032WV | 22 | | GA | 8-7 | 33-25-12 | D05950 | | | 2 | | SM00032 | | 9 | ALL | |
| 0033WG | 22 | | GA | 8-7 | 33-25-12 | D05950 | | | 3 | | SM00033 | | 9 | ALL | |
| 0034WO | 22 | | GA | 8-7 | 33-25-12 | D05950 | | | 4 | | SM00034 | | 9 | ALL | |
| 0035V | 22 | | GA | 8-7 | 33-25-12 | D05950 | | | 5 | | SM00035 | | 9 | ALL | |
| 0036WN | 16 | | GA | 8-7 | 33-23-12 | D05950 | | | 6 | | SM00036 | | 9 | ALL | |
| 0037W | 20 | | GA | 8-7 | 33-24-13 | D05950 | | | 7 | | SM00037 | | 9 | ALL | |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 27

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|-------|-----|--------------------------------------|----------|---------|--------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3704 | 286N3704 | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | | | |
| 0038WP | 16 | GA | | 8-7 | 33-23-12 | | D05950 | | | 8 | | | SM00038 | | 9 | | ALL |
| 0039AJ | 20 | GA | | 8-7 | 35-21-12 | | D05950 | | | 11 | | | SM00039 | | 9 | | ALL |
| 0040K | 18 | GA | | 8-7 | 35-21-12 | | D05950 | | | 10 | | | SM00040 | | 9 | | ALL |
| 0041G | 16 | GA | | 12-3 | 33-24-13 | | D05952 | | | 1 | | | SM00031 | | 9 | | 001-099 |
| 0041G | 16 | GA | | 10-10 | 33-24-13 | | D05952 | | | 1 | | | SM00031 | | 9 | | 115-199 |
| 0042WV | 22 | GA | | 12-3 | 33-25-12 | | D05952 | | | 2 | | | SM00032 | | 9 | | 001-099 |
| 0042WV | 22 | GA | | 10-10 | 33-25-12 | | D05952 | | | 2 | | | SM00032 | | 9 | | 115-199 |
| 0043WG | 22 | GA | | 12-3 | 33-25-12 | | D05952 | | | 3 | | | SM00033 | | 9 | | 001-099 |
| 0043WG | 22 | GA | | 10-10 | 33-25-12 | | D05952 | | | 3 | | | SM00033 | | 9 | | 115-199 |
| 0044WO | 22 | GA | | 12-3 | 33-25-12 | | D05952 | | | 4 | | | SM00034 | | 9 | | 001-099 |
| 0044WO | 22 | GA | | 10-10 | 33-25-12 | | D05952 | | | 4 | | | SM00034 | | 9 | | 115-199 |
| 0045V | 22 | GA | | 12-3 | 33-25-12 | | D05952 | | | 5 | | | SM00035 | | 9 | | 001-099 |
| 0045V | 22 | GA | | 10-10 | 33-25-12 | | D05952 | | | 5 | | | SM00035 | | 9 | | 115-199 |
| 0046WN | 16 | GA | | 12-3 | 33-23-12 | | D05952 | | | 6 | | | SM00036 | | 9 | | 001-099 |
| 0046WN | 16 | GA | | 10-10 | 33-23-12 | | D05952 | | | 6 | | | SM00036 | | 9 | | 115-199 |
| 0047W | 20 | GA | | 12-3 | 33-24-13 | | D05952 | | | 7 | | | SM00037 | | 9 | | 001-099 |
| 0047W | 20 | GA | | 10-10 | 33-24-13 | | D05952 | | | 7 | | | SM00037 | | 9 | | 115-199 |
| 0048WP | 16 | GA | | 12-3 | 33-23-12 | | D05952 | | | 8 | | | SM00038 | | 9 | | 001-099 |
| 0048WP | 16 | GA | | 10-10 | 33-23-12 | | D05952 | | | 8 | | | SM00038 | | 9 | | 115-199 |
| 0049AJ | 20 | GA | | 12-3 | 35-21-12 | | D05952 | | | 11 | | | SM00039 | | 9 | | 001-099 |
| 0049AJ | 20 | GA | | 10-10 | 35-21-12 | | D05952 | | | 11 | | | SM00039 | | 9 | | 115-199 |
| 0050K | 18 | GA | | 12-3 | 35-21-12 | | D05952 | | | 10 | | | SM00040 | | 9 | | 001-099 |
| 0050K | 18 | GA | | 10-10 | 35-21-12 | | D05952 | | | 10 | | | SM00040 | | 9 | | 115-199 |
| 0051G | 16 | GA | | 12-2 | 33-24-13 | | D05954 | | | 1 | | | SM00051 | | 9 | | 001-099 |
| 0051G | 16 | GA | | 8-9 | 33-24-13 | | D05954 | | | 1 | | | SM00051 | | 9 | | 115-199 |
| 0052WV | 22 | GA | | 12-2 | 33-25-13 | | D05954 | | | 2 | | | SM00052 | | 9 | | 001-099 |
| 0052WV | 22 | GA | | 8-9 | 33-25-13 | | D05954 | | | 2 | | | SM00052 | | 9 | | 115-199 |
| 0053WG | 22 | GA | | 12-2 | 33-25-13 | | D05954 | | | 3 | | | SM00053 | | 9 | | 001-099 |
| 0053WG | 22 | GA | | 8-9 | 33-25-13 | | D05954 | | | 3 | | | SM00053 | | 9 | | 115-199 |
| 0055V | 22 | GA | | 12-2 | 33-25-13 | | D05954 | | | 5 | | | SM00055 | | 9 | | 001-099 |
| 0055V | 22 | GA | | 8-9 | 33-25-13 | | D05954 | | | 5 | | | SM00055 | | 9 | | 115-199 |
| 0056WN | 16 | GA | | 12-2 | 33-23-13 | | D05954 | | | 6 | | | SM00056 | | 9 | | 001-099 |
| 0056WN | 16 | GA | | 8-9 | 33-23-13 | | D05954 | | | 6 | | | SM00056 | | 9 | | 115-199 |
| 0057W | 20 | GA | | 12-2 | 33-24-13 | | D05954 | | | 7 | | | SM00057 | | 9 | | 001-099 |
| 0057W | 20 | GA | | 8-9 | 33-24-13 | | D05954 | | | 7 | | | SM00057 | | 9 | | 115-199 |
| 0058WP | 16 | GA | | 12-2 | 33-23-13 | | D05954 | | | 8 | | | SM00058 | | 9 | | 001-099 |
| 0058WP | 16 | GA | | 8-9 | 33-23-13 | | D05954 | | | 8 | | | SM00058 | | 9 | | 115-199 |
| 0059AJ | 20 | GA | | 12-2 | 35-21-13 | | D05954 | | | 11 | | | SM00059 | | 9 | | 001-099 |
| 0059AJ | 20 | GA | | 8-9 | 35-21-13 | | D05954 | | | 11 | | | SM00059 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 28

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3704 | | 286N3704 | | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | |
| 0060K | 18 | GA | | | 12-2 | 35-21-13 | D05954 | 10 | | | SM00060 | 9 | | | 001-099 |
| 0060K | 18 | GA | | | 8-9 | 35-21-13 | D05954 | 10 | | | SM00060 | 9 | | | 115-199 |
| 0061G | 16 | GA | | | 13-4 | 33-24-13 | D05956 | 1 | | | SM00051 | 9 | | | 001-099 |
| 0061G | 16 | GA | | | 9-8 | 33-24-13 | D05956 | 1 | | | SM00051 | 9 | | | 115-199 |
| 0062WV | 22 | GA | | | 13-4 | 33-25-13 | D05956 | 2 | | | SM00052 | 9 | | | 001-099 |
| 0062WV | 22 | GA | | | 9-8 | 33-25-13 | D05956 | 2 | | | SM00052 | 9 | | | 115-199 |
| 0063WG | 22 | GA | | | 13-4 | 33-25-13 | D05956 | 3 | | | SM00053 | 9 | | | 001-099 |
| 0063WG | 22 | GA | | | 9-8 | 33-25-13 | D05956 | 3 | | | SM00053 | 9 | | | 115-199 |
| 0065V | 22 | GA | | | 13-4 | 33-25-13 | D05956 | 5 | | | SM00055 | 9 | | | 001-099 |
| 0065V | 22 | GA | | | 9-8 | 33-25-13 | D05956 | 5 | | | SM00055 | 9 | | | 115-199 |
| 0066WN | 16 | GA | | | 13-4 | 33-23-13 | D05956 | 6 | | | SM00056 | 9 | | | 001-099 |
| 0066WN | 16 | GA | | | 9-8 | 33-23-13 | D05956 | 6 | | | SM00056 | 9 | | | 115-199 |
| 0067W | 20 | GA | | | 13-4 | 33-24-13 | D05956 | 7 | | | SM00057 | 9 | | | 001-099 |
| 0067W | 20 | GA | | | 9-8 | 33-24-13 | D05956 | 7 | | | SM00057 | 9 | | | 115-199 |
| 0068WP | 16 | GA | | | 13-4 | 33-23-13 | D05956 | 8 | | | SM00058 | 9 | | | 001-099 |
| 0068WP | 16 | GA | | | 9-8 | 33-23-13 | D05956 | 8 | | | SM00058 | 9 | | | 115-199 |
| 0069AJ | 20 | GA | | | 13-4 | 35-21-13 | D05956 | 11 | | | SM00059 | 9 | | | 001-099 |
| 0069AJ | 20 | GA | | | 9-8 | 35-21-13 | D05956 | 11 | | | SM00059 | 9 | | | 115-199 |
| 0070K | 18 | GA | | | 13-4 | 35-21-13 | D05956 | 10 | | | SM00060 | 9 | | | 001-099 |
| 0070K | 18 | GA | | | 9-8 | 35-21-13 | D05956 | 10 | | | SM00060 | 9 | | | 115-199 |
| 0071G | 16 | GA | | | 7-11 | 33-24-13 | D05958 | 1 | | | SM00071 | 9 | | | 001-099 |
| 0071G | 16 | GA | | | 7-1 | 33-24-13 | D05958 | 1 | | | SM00071 | 9 | | | 115-199 |
| 0072WV | 22 | GA | | | 7-11 | 33-25-13 | D05958 | 2 | | | SM00072 | 9 | | | 001-099 |
| 0072WV | 22 | GA | | | 7-1 | 33-25-13 | D05958 | 2 | | | SM00072 | 9 | | | 115-199 |
| 0073WG | 22 | GA | | | 7-11 | 33-25-13 | D05958 | 3 | | | SM00073 | 9 | | | 001-099 |
| 0073WG | 22 | GA | | | 7-1 | 33-25-13 | D05958 | 3 | | | SM00073 | 9 | | | 115-199 |
| 0075V | 22 | GA | | | 7-11 | 33-25-13 | D05958 | 5 | | | SM00075 | 9 | | | 001-099 |
| 0075V | 22 | GA | | | 7-1 | 33-25-13 | D05958 | 5 | | | SM00075 | 9 | | | 115-199 |
| 0076WN | 16 | GA | | | 7-11 | 33-23-13 | D05958 | 6 | | | SM00076 | 9 | | | 001-099 |
| 0076WN | 16 | GA | | | 7-1 | 33-23-13 | D05958 | 6 | | | SM00076 | 9 | | | 115-199 |
| 0077W | 20 | GA | | | 7-11 | 33-24-13 | D05958 | 7 | | | SM00077 | 9 | | | 001-099 |
| 0077W | 20 | GA | | | 7-1 | 33-24-13 | D05958 | 7 | | | SM00077 | 9 | | | 115-199 |
| 0078WP | 16 | GA | | | 7-11 | 33-23-13 | D05958 | 8 | | | SM00078 | 9 | | | 001-099 |
| 0078WP | 16 | GA | | | 7-1 | 33-23-13 | D05958 | 8 | | | SM00078 | 9 | | | 115-199 |
| 0079AJ | 20 | GA | | | 7-11 | 35-21-13 | D05958 | 11 | | | SM00079 | 9 | | | 001-099 |
| 0079AJ | 20 | GA | | | 7-1 | 35-21-13 | D05958 | 11 | | | SM00079 | 9 | | | 115-199 |
| 0080K | 18 | GA | | | 7-11 | 35-21-13 | D05958 | 10 | | | SM00080 | 9 | | | 001-099 |
| 0080K | 18 | GA | | | 7-1 | 35-21-13 | D05958 | 10 | | | SM00080 | 9 | | | 115-199 |
| 0081G | 16 | GA | | | 10-10 | 33-24-13 | D05960 | 1 | | | SM00071 | 9 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 29

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3704 | 286N3704 | | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | |
| 0081G | 16 | | GA | | 10-1 | 33-24-13 | D05960 | | | | | SM00071 | | 9 | | 115-199 |
| 0082WV | 22 | | GA | | 10-10 | 33-25-13 | D05960 | | | | | SM00072 | | 9 | | 001-099 |
| 0082WV | 22 | | GA | | 10-1 | 33-25-13 | D05960 | | | | | SM00072 | | 9 | | 115-199 |
| 0083WG | 22 | | GA | | 10-10 | 33-25-13 | D05960 | | | | | SM00073 | | 9 | | 001-099 |
| 0083WG | 22 | | GA | | 10-1 | 33-25-13 | D05960 | | | | | SM00073 | | 9 | | 115-199 |
| 0085V | 22 | | GA | | 10-10 | 33-25-13 | D05960 | | | | | SM00075 | | 9 | | 001-099 |
| 0085V | 22 | | GA | | 10-1 | 33-25-13 | D05960 | | | | | SM00075 | | 9 | | 115-199 |
| 0086WN | 16 | | GA | | 10-10 | 33-23-13 | D05960 | | | | | SM00076 | | 9 | | 001-099 |
| 0086WN | 16 | | GA | | 10-1 | 33-23-13 | D05960 | | | | | SM00076 | | 9 | | 115-199 |
| 0087W | 20 | | GA | | 10-10 | 33-24-13 | D05960 | | | | | SM00077 | | 9 | | 001-099 |
| 0087W | 20 | | GA | | 10-1 | 33-24-13 | D05960 | | | | | SM00077 | | 9 | | 115-199 |
| 0088WP | 16 | | GA | | 10-10 | 33-23-13 | D05960 | | | | | SM00078 | | 9 | | 001-099 |
| 0088WP | 16 | | GA | | 10-1 | 33-23-13 | D05960 | | | | | SM00078 | | 9 | | 115-199 |
| 0089AJ | 20 | | GA | | 10-10 | 35-21-13 | D05960 | | | | | SM00079 | | 9 | | 001-099 |
| 0089AJ | 20 | | GA | | 10-1 | 35-21-13 | D05960 | | | | | SM00079 | | 9 | | 115-199 |
| 0090K | 18 | | GA | | 10-10 | 35-21-13 | D05960 | | | | | SM00080 | | 9 | | 001-099 |
| 0090K | 18 | | GA | | 10-1 | 35-21-13 | D05960 | | | | | SM00080 | | 9 | | 115-199 |
| 0091G | 16 | | GA | | 9-1 | 33-24-13 | D05962 | | | | | SM00091 | | 9 | | 001-099 |
| 0091G | 16 | | GA | | 8-3 | 33-24-13 | D05962 | | | | | SM00091 | | 9 | | 115-199 |
| 0092WV | 22 | | GA | | 9-1 | 33-25-13 | D05962 | | | | | SM00092 | | 9 | | 001-099 |
| 0092WV | 22 | | GA | | 8-3 | 33-25-13 | D05962 | | | | | SM00092 | | 9 | | 115-199 |
| 0093WG | 22 | | GA | | 9-1 | 33-25-13 | D05962 | | | | | SM00093 | | 9 | | 001-099 |
| 0093WG | 22 | | GA | | 8-3 | 33-25-13 | D05962 | | | | | SM00093 | | 9 | | 115-199 |
| 0095V | 22 | | GA | | 9-1 | 33-25-13 | D05962 | | | | | SM00095 | | 9 | | 001-099 |
| 0095V | 22 | | GA | | 8-3 | 33-25-13 | D05962 | | | | | SM00095 | | 9 | | 115-199 |
| 0096WN | 16 | | GA | | 9-1 | 33-23-13 | D05962 | | | | | SM00096 | | 9 | | 001-099 |
| 0096WN | 16 | | GA | | 8-3 | 33-23-13 | D05962 | | | | | SM00096 | | 9 | | 115-199 |
| 0097W | 20 | | GA | | 9-1 | 33-24-13 | D05962 | | | | | SM00097 | | 9 | | 001-099 |
| 0097W | 20 | | GA | | 8-3 | 33-24-13 | D05962 | | | | | SM00097 | | 9 | | 115-199 |
| 0098WP | 16 | | GA | | 9-1 | 33-23-13 | D05962 | | | | | SM00098 | | 9 | | 001-099 |
| 0098WP | 16 | | GA | | 8-3 | 33-23-13 | D05962 | | | | | SM00098 | | 9 | | 115-199 |
| 0099AJ | 20 | | GA | | 9-1 | 35-21-13 | D05962 | | | | | SM00099 | | 9 | | 001-099 |
| 0099AJ | 20 | | GA | | 8-3 | 35-21-13 | D05962 | | | | | SM00099 | | 9 | | 115-199 |
| 0100K | 18 | | GA | | 9-1 | 35-21-13 | D05962 | | | | | SM00100 | | 9 | | 001-099 |
| 0100K | 18 | | GA | | 8-3 | 35-21-13 | D05962 | | | | | SM00100 | | 9 | | 115-199 |
| 0101G | 16 | | GA | | 11-2 | 33-24-13 | D05964 | | | | | SM00091 | | 9 | | 001-099 |
| 0101G | 16 | | GA | | 10-4 | 33-24-13 | D05964 | | | | | SM00091 | | 9 | | 115-199 |
| 0102WV | 22 | | GA | | 11-2 | 33-25-13 | D05964 | | | | | SM00092 | | 9 | | 001-099 |
| 0102WV | 22 | | GA | | 10-4 | 33-25-13 | D05964 | | | | | SM00092 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 30

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3704 | 286N3704 | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | |
| 0103WG | 22 | | GA | | 11-2 | 33-25-13 | D05964 | | 3 | | SM00093 | | 9 | | 001-099 |
| 0103WG | 22 | | GA | | 10-4 | 33-25-13 | D05964 | | 3 | | SM00093 | | 9 | | 115-199 |
| 0105V | 22 | | GA | | 11-2 | 33-25-13 | D05964 | | 5 | | SM00095 | | 9 | | 001-099 |
| 0105V | 22 | | GA | | 10-4 | 33-25-13 | D05964 | | 5 | | SM00095 | | 9 | | 115-199 |
| 0106WN | 16 | | GA | | 11-2 | 33-23-13 | D05964 | | 6 | | SM00096 | | 9 | | 001-099 |
| 0106WN | 16 | | GA | | 10-4 | 33-23-13 | D05964 | | 6 | | SM00096 | | 9 | | 115-199 |
| 0107W | 20 | | GA | | 11-2 | 33-24-13 | D05964 | | 7 | | SM00097 | | 9 | | 001-099 |
| 0107W | 20 | | GA | | 10-4 | 33-24-13 | D05964 | | 7 | | SM00097 | | 9 | | 115-199 |
| 0108WP | 16 | | GA | | 11-2 | 33-23-13 | D05964 | | 8 | | SM00098 | | 9 | | 001-099 |
| 0108WP | 16 | | GA | | 10-4 | 33-23-13 | D05964 | | 8 | | SM00098 | | 9 | | 115-199 |
| 0109AJ | 20 | | GA | | 11-2 | 35-21-13 | D05964 | | 11 | | SM00099 | | 9 | | 001-099 |
| 0109AJ | 20 | | GA | | 10-4 | 35-21-13 | D05964 | | 11 | | SM00099 | | 9 | | 115-199 |
| 0110K | 18 | | GA | | 11-2 | 35-21-13 | D05964 | | 10 | | SM00100 | | 9 | | 001-099 |
| 0110K | 18 | | GA | | 10-4 | 35-21-13 | D05964 | | 10 | | SM00100 | | 9 | | 115-199 |
| 0111G | 16 | | GA | | 9-6 | 33-24-13 | D05966 | | 1 | | SM00111 | | 9 | | 001-099 |
| 0111G | 16 | | GA | | 8-3 | 33-24-13 | D05966 | | 1 | | SM00111 | | 9 | | 115-199 |
| 0112WV | 22 | | GA | | 9-6 | 33-25-13 | D05966 | | 2 | | SM00112 | | 9 | | 001-099 |
| 0112WV | 22 | | GA | | 8-3 | 33-25-13 | D05966 | | 2 | | SM00112 | | 9 | | 115-199 |
| 0113WG | 22 | | GA | | 9-6 | 33-25-13 | D05966 | | 3 | | SM00113 | | 9 | | 001-099 |
| 0113WG | 22 | | GA | | 8-3 | 33-25-13 | D05966 | | 3 | | SM00113 | | 9 | | 115-199 |
| 0115V | 22 | | GA | | 9-6 | 33-25-13 | D05966 | | 5 | | SM00115 | | 9 | | 001-099 |
| 0115V | 22 | | GA | | 8-3 | 33-25-13 | D05966 | | 5 | | SM00115 | | 9 | | 115-199 |
| 0116WN | 16 | | GA | | 9-6 | 33-23-13 | D05966 | | 6 | | SM00116 | | 9 | | 001-099 |
| 0116WN | 16 | | GA | | 8-3 | 33-23-13 | D05966 | | 6 | | SM00116 | | 9 | | 115-199 |
| 0117W | 20 | | GA | | 9-6 | 33-24-13 | D05966 | | 7 | | SM00117 | | 9 | | 001-099 |
| 0117W | 20 | | GA | | 8-3 | 33-24-13 | D05966 | | 7 | | SM00117 | | 9 | | 115-199 |
| 0118WP | 16 | | GA | | 9-6 | 33-23-13 | D05966 | | 8 | | SM00118 | | 9 | | 001-099 |
| 0118WP | 16 | | GA | | 8-3 | 33-23-13 | D05966 | | 8 | | SM00118 | | 9 | | 115-199 |
| 0119AJ | 20 | | GA | | 9-6 | 35-21-13 | D05966 | | 11 | | SM00119 | | 9 | | 001-099 |
| 0119AJ | 20 | | GA | | 8-3 | 35-21-13 | D05966 | | 11 | | SM00119 | | 9 | | 115-199 |
| 0120K | 18 | | GA | | 9-6 | 35-21-13 | D05966 | | 10 | | SM00120 | | 9 | | 001-099 |
| 0120K | 18 | | GA | | 8-3 | 35-21-13 | D05966 | | 10 | | SM00120 | | 9 | | 115-199 |
| 0411G | 16 | | GA | | 4-4 | 33-24-13 | SM00011 | | | 9 | SM00031 | | 9 | | 001-099 |
| 0411G | 16 | | GA | | 4-1 | 33-24-13 | SM00011 | | | 9 | SM00031 | | 9 | | 115-199 |
| 0412WV | 22 | | GA | | 4-4 | 33-25-12 | SM00012 | | | 9 | SM00032 | | 9 | | 001-099 |
| 0412WV | 22 | | GA | | 4-1 | 33-25-12 | SM00012 | | | 9 | SM00032 | | 9 | | 115-199 |
| 0413WG | 22 | | GA | | 4-4 | 33-25-12 | SM00013 | | | 9 | SM00033 | | 9 | | 001-099 |
| 0413WG | 22 | | GA | | 4-1 | 33-25-12 | SM00013 | | | 9 | SM00033 | | 9 | | 115-199 |
| 0414WO | 22 | | GA | | 4-4 | 33-25-12 | SM00014 | | | 9 | SM00034 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 31

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|-------|---------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3704 | 286N3704 | | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | |
| 0414WO | 22 | | GA | | 4-1 | 33-25-12 | | SM00014 | | | | 9 | SM00034 | | | 115-199 |
| 0415V | 22 | | GA | | 4-4 | 33-25-12 | | SM00015 | | | | 9 | SM00035 | | | 001-099 |
| 0415V | 22 | | GA | | 4-1 | 33-25-12 | | SM00015 | | | | 9 | SM00035 | | | 115-199 |
| 0416WN | 16 | | GA | | 4-4 | 33-23-12 | | SM00016 | | | | 9 | SM00036 | | | 001-099 |
| 0416WN | 16 | | GA | | 4-1 | 33-23-12 | | SM00016 | | | | 9 | SM00036 | | | 115-199 |
| 0417W | 20 | | GA | | 4-4 | 33-24-13 | | SM00017 | | | | 9 | SM00037 | | | 001-099 |
| 0417W | 20 | | GA | | 4-1 | 33-24-13 | | SM00017 | | | | 9 | SM00037 | | | 115-199 |
| 0418WP | 16 | | GA | | 4-4 | 33-23-12 | | SM00018 | | | | 9 | SM00038 | | | 001-099 |
| 0418WP | 16 | | GA | | 4-1 | 33-23-12 | | SM00018 | | | | 9 | SM00038 | | | 115-199 |
| 0419AJ | 16 | | GA | | 4-4 | 35-21-12 | | SM00019 | | | | 9 | SM00039 | | | 001-099 |
| 0419AJ | 16 | | GA | | 4-1 | 35-21-12 | | SM00019 | | | | 9 | SM00039 | | | 115-199 |
| 0420K | 18 | | GA | | 4-4 | 35-21-12 | | SM00020 | | | | 9 | SM00040 | | | 001-099 |
| 0420K | 18 | | GA | | 4-1 | 35-21-12 | | SM00020 | | | | 9 | SM00040 | | | 115-199 |
| 0431G | 16 | | GA | | 3-6 | 33-24-13 | | SM00031 | | | | 9 | SM00051 | | | 001-099 |
| 0431G | 16 | | GA | | 5-2 | 33-24-13 | | SM00031 | | | | 9 | SM00051 | | | 115-199 |
| 0432WV | 22 | | GA | | 3-6 | 33-25-12 | | SM00032 | | | | 9 | SM00052 | | | 001-099 |
| 0432WV | 22 | | GA | | 5-2 | 33-25-12 | | SM00032 | | | | 9 | SM00052 | | | 115-199 |
| 0433WG | 22 | | GA | | 5-2 | 33-25-12 | | SM00033 | | | | 9 | SM00053 | | | 115-199 |
| 0437W | 20 | | GA | | 3-6 | 33-24-13 | | SM00037 | | | | 9 | SM00057 | | | 001-099 |
| 0437W | 20 | | GA | | 5-2 | 33-24-13 | | SM00037 | | | | 9 | SM00057 | | | 115-199 |
| 0438WP | 16 | | GA | | 3-6 | 33-23-12 | | SM00038 | | | | 9 | SM00058 | | | 001-099 |
| 0438WP | 16 | | GA | | 5-2 | 33-23-12 | | SM00038 | | | | 9 | SM00058 | | | 115-199 |
| 0440K | 18 | | GA | | 3-6 | 35-21-13 | | SM00040 | | | | 9 | SM00060 | | | 001-099 |
| 0440K | 18 | | GA | | 5-2 | 35-21-13 | | SM00040 | | | | 9 | SM00060 | | | 115-199 |
| 0451G | 16 | | GA | | 10-9 | 33-24-13 | | SM00051 | | | | 9 | SM00071 | | | 001-099 |
| 0451G | 16 | | GA | | 6-4 | 33-24-13 | | SM00051 | | | | 9 | SM00071 | | | 115-199 |
| 0452WV | 22 | | GA | | 10-9 | 33-25-13 | | SM00052 | | | | 9 | SM00072 | | | 001-099 |
| 0452WV | 22 | | GA | | 6-4 | 33-25-13 | | SM00052 | | | | 9 | SM00072 | | | 115-199 |
| 0453WG | 22 | | GA | | 10-9 | 33-25-13 | | SM00053 | | | | 9 | SM00073 | | | 001-099 |
| 0453WG | 22 | | GA | | 6-4 | 33-25-13 | | SM00053 | | | | 9 | SM00073 | | | 115-199 |
| 0455V | 22 | | GA | | 10-9 | 33-25-13 | | SM00055 | | | | 9 | SM00075 | | | 001-099 |
| 0455V | 22 | | GA | | 6-4 | 33-25-13 | | SM00055 | | | | 9 | SM00075 | | | 115-199 |
| 0456WN | 16 | | GA | | 10-9 | 33-23-13 | | SM00056 | | | | 9 | SM00076 | | | 001-099 |
| 0456WN | 16 | | GA | | 6-4 | 33-23-13 | | SM00056 | | | | 9 | SM00076 | | | 115-199 |
| 0457W | 20 | | GA | | 10-9 | 33-24-13 | | SM00057 | | | | 9 | SM00077 | | | 001-099 |
| 0457W | 20 | | GA | | 6-4 | 33-24-13 | | SM00057 | | | | 9 | SM00077 | | | 115-199 |
| 0458WP | 16 | | GA | | 10-9 | 33-23-13 | | SM00058 | | | | 9 | SM00078 | | | 001-099 |
| 0458WP | 16 | | GA | | 6-4 | 33-23-13 | | SM00058 | | | | 9 | SM00078 | | | 115-199 |
| 0459AJ | 16 | | GA | | 10-9 | 35-21-13 | | SM00059 | | | | 9 | SM00079 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 32

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|-------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3704 | 286N3704 | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | |
| 0459AJ | 16 | GA | | | 6-4 | 35-21-13 | SM00059 | | | | 9 | | | | 115-199 |
| 0460K | 18 | GA | | | 10-9 | 35-21-13 | SM00060 | | | | 9 | | | | 001-099 |
| 0460K | 18 | GA | | | 6-4 | 35-21-13 | SM00060 | | | | 9 | | | | 115-199 |
| 0471G | 16 | GA | | | 7-8 | 33-24-13 | SM00071 | | | | 9 | | | | 001-099 |
| 0471G | 16 | GA | | | 6-0 | 33-24-13 | SM00071 | | | | 9 | | | | 115-199 |
| 0472WV | 22 | GA | | | 7-8 | 33-25-13 | SM00072 | | | | 9 | | | | 001-099 |
| 0472WV | 22 | GA | | | 6-0 | 33-25-13 | SM00072 | | | | 9 | | | | 115-199 |
| 0473WG | 22 | GA | | | 7-8 | 33-25-13 | SM00073 | | | | 9 | | | | 001-099 |
| 0473WG | 22 | GA | | | 6-0 | 33-25-13 | SM00073 | | | | 9 | | | | 115-199 |
| 0475V | 22 | GA | | | 7-8 | 33-25-13 | SM00075 | | | | 9 | | | | 001-099 |
| 0475V | 22 | GA | | | 6-0 | 33-25-13 | SM00075 | | | | 9 | | | | 115-199 |
| 0476WN | 16 | GA | | | 7-8 | 33-23-13 | SM00076 | | | | 9 | | | | 001-099 |
| 0476WN | 16 | GA | | | 6-0 | 33-23-13 | SM00076 | | | | 9 | | | | 115-199 |
| 0477W | 20 | GA | | | 7-8 | 33-24-13 | SM00077 | | | | 9 | | | | 001-099 |
| 0477W | 20 | GA | | | 6-0 | 33-24-13 | SM00077 | | | | 9 | | | | 115-199 |
| 0478WP | 16 | GA | | | 7-8 | 33-23-13 | SM00078 | | | | 9 | | | | 001-099 |
| 0478WP | 16 | GA | | | 6-0 | 33-23-13 | SM00078 | | | | 9 | | | | 115-199 |
| 0479AJ | 16 | GA | | | 7-8 | 35-21-13 | SM00079 | | | | 9 | | | | 001-099 |
| 0479AJ | 16 | GA | | | 6-0 | 35-21-13 | SM00079 | | | | 9 | | | | 115-199 |
| 0480K | 18 | GA | | | 7-8 | 35-21-13 | SM00080 | | | | 9 | | | | 001-099 |
| 0480K | 18 | GA | | | 6-0 | 35-21-13 | SM00080 | | | | 9 | | | | 115-199 |
| 0491G | 16 | GA | | | 7-10 | 33-24-13 | SM00091 | | | | 9 | | | | 001-099 |
| 0491G | 16 | GA | | | 5-5 | 33-24-13 | SM00091 | | | | 9 | | | | 115-199 |
| 0492WV | 22 | GA | | | 7-10 | 33-25-13 | SM00092 | | | | 9 | | | | 001-099 |
| 0492WV | 22 | GA | | | 5-5 | 33-25-13 | SM00092 | | | | 9 | | | | 115-199 |
| 0493WG | 22 | GA | | | 7-10 | 33-25-13 | SM00093 | | | | 9 | | | | 001-099 |
| 0493WG | 22 | GA | | | 5-5 | 33-25-13 | SM00093 | | | | 9 | | | | 115-199 |
| 0495V | 22 | GA | | | 7-10 | 33-25-13 | SM00095 | | | | 9 | | | | 001-099 |
| 0495V | 22 | GA | | | 5-5 | 33-25-13 | SM00095 | | | | 9 | | | | 115-199 |
| 0496WN | 16 | GA | | | 7-10 | 33-23-13 | SM00096 | | | | 9 | | | | 001-099 |
| 0496WN | 16 | GA | | | 5-5 | 33-23-13 | SM00096 | | | | 9 | | | | 115-199 |
| 0497W | 20 | GA | | | 7-10 | 33-24-13 | SM00097 | | | | 9 | | | | 001-099 |
| 0497W | 20 | GA | | | 5-5 | 33-24-13 | SM00097 | | | | 9 | | | | 115-199 |
| 0498WP | 16 | GA | | | 7-10 | 33-23-13 | SM00098 | | | | 9 | | | | 001-099 |
| 0498WP | 16 | GA | | | 5-5 | 33-23-13 | SM00098 | | | | 9 | | | | 115-199 |
| 0499AJ | 16 | GA | | | 7-10 | 35-21-13 | SM00099 | | | | 9 | | | | 001-099 |
| 0499AJ | 16 | GA | | | 5-5 | 35-21-13 | SM00099 | | | | 9 | | | | 115-199 |
| 0500K | 18 | GA | | | 7-10 | 35-21-13 | SM00100 | | | | 9 | | | | 001-099 |
| 0500K | 18 | GA | | | 5-5 | 35-21-13 | SM00100 | | | | 9 | | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 33

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3704 | 286N3704 | | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | | |
| 0800 | 22 | | GA | | 26-4 | 23-31-41 | D40314J | | 12 | | | D40312P | | 12 | | 001-099 | |
| 0800 | 22 | | GA | | 25-3 | 23-31-41 | D40312P | | 12 | | | D40314J | | 12 | | 115-199 | |
| 0801 | 16 | | GA | | 4-9 | 33-24-13 | D40314J | | 1 | | | SM00111 | | 9 | | 001-099 | |
| 0801 | 16 | | GA | | 2-6 | 33-24-13 | D40314J | | 1 | | | SM00111 | | 9 | | 115-199 | |
| 0802 | 22 | | GA | | 4-9 | 33-25-13 | D40314J | | 2 | | | SM00112 | | 9 | | 001-099 | |
| 0802 | 22 | | GA | | 2-6 | 33-25-13 | D40314J | | 2 | | | SM00112 | | 9 | | 115-199 | |
| 0803 | 22 | | GA | | 4-9 | 33-25-13 | D40314J | | 3 | | | SM00113 | | 9 | | 001-099 | |
| 0803 | 22 | | GA | | 2-6 | 33-25-13 | D40314J | | 3 | | | SM00113 | | 9 | | 115-199 | |
| 0805 | 22 | | GA | | 4-9 | 33-25-13 | D40314J | | 5 | | | SM00115 | | 9 | | 001-099 | |
| 0805 | 22 | | GA | | 2-6 | 33-25-13 | D40314J | | 5 | | | SM00115 | | 9 | | 115-199 | |
| 0806 | 16 | | GA | | 4-9 | 33-23-13 | D40314J | | 6 | | | SM00116 | | 9 | | 001-099 | |
| 0806 | 16 | | GA | | 2-6 | 33-23-13 | D40314J | | 6 | | | SM00116 | | 9 | | 115-199 | |
| 0807 | 20 | | GA | | 4-9 | 33-24-13 | D40314J | | 7 | | | SM00117 | | 9 | | 001-099 | |
| 0807 | 20 | | GA | | 2-6 | 33-24-13 | D40314J | | 7 | | | SM00117 | | 9 | | 115-199 | |
| 0808 | 16 | | GA | | 4-9 | 33-23-13 | D40314J | | 8 | | | SM00118 | | 9 | | 001-099 | |
| 0808 | 16 | | GA | | 2-6 | 33-23-13 | D40314J | | 8 | | | SM00118 | | 9 | | 115-199 | |
| 0809 | 16 | | GA | | 4-9 | 35-21-13 | SM00119 | | 9 | | | D40314J | | 9 | | 001-099 | |
| 0809 | 16 | | GA | | 2-6 | 35-21-13 | SM00119 | | 9 | | | D40314J | | 9 | | 115-199 | |
| 0810 | 18 | | GA | | 4-9 | 35-21-13 | SM00120 | | 9 | | | D40314J | | 10 | | 001-099 | |
| 0810 | 18 | | GA | | 2-6 | 35-21-13 | SM00120 | | 9 | | | D40314J | | 10 | | 115-199 | |
| 0811 | 16 | | GA | | 3-1 | 33-24-13 | D40312P | | 1 | | | SM00011 | | 9 | | 001-099 | |
| 0811 | 16 | | GA | | 2-11 | 33-24-13 | D40312P | | 1 | | | SM00011 | | 9 | | 115-199 | |
| 0812 | 22 | | GA | | 3-1 | 33-25-12 | D40312P | | 2 | | | SM00012 | | 9 | | 001-099 | |
| 0812 | 22 | | GA | | 2-11 | 33-25-12 | D40312P | | 2 | | | SM00012 | | 9 | | 115-199 | |
| 0813 | 22 | | GA | | 3-1 | 33-25-12 | D40312P | | 3 | | | SM00013 | | 9 | | 001-099 | |
| 0813 | 22 | | GA | | 2-11 | 33-25-12 | D40312P | | 3 | | | SM00013 | | 9 | | 115-199 | |
| 0814 | 22 | | GA | | 3-1 | 33-25-12 | D40312P | | 4 | | | SM00014 | | 9 | | 001-099 | |
| 0814 | 22 | | GA | | 2-11 | 33-25-12 | D40312P | | 4 | | | SM00014 | | 9 | | 115-199 | |
| 0815 | 22 | | GA | | 3-1 | 33-25-12 | D40312P | | 5 | | | SM00015 | | 9 | | 001-099 | |
| 0815 | 22 | | GA | | 2-11 | 33-25-12 | D40312P | | 5 | | | SM00015 | | 9 | | 115-199 | |
| 0817 | 20 | | GA | | 3-1 | 33-24-13 | D40312P | | 7 | | | SM00017 | | 9 | | 001-099 | |
| 0817 | 20 | | GA | | 2-11 | 33-24-13 | D40312P | | 7 | | | SM00017 | | 9 | | 115-199 | |
| 0822 | 16 | | GA | | 26-4 | SPARE | D40312P | | 22 | | | D40314J | | 19 | | 001-099 | |
| 0822 | 16 | | GA | | 25-3 | SPARE | D40312P | | 22 | | | D40314J | | 18 | | 115-199 | |
| 0826 | 22 | | GA | | 26-4 | 23-31-41 | D40312P | | 26 | | | D40314J | | 16 | | 001-099 | |
| 0826 | 22 | | GA | | 25-3 | 23-31-41 | D40312P | | 26 | | | D40314J | | 16 | | 115-199 | |
| 0829 | 16 | | GA | | 6-6 | 35-21-13 | D40312P | | 29 | | | SM00059 | | 9 | | 001-099 | |
| 0829 | 16 | | GA | | 8-2 | 35-21-13 | D40312P | | 29 | | | SM00059 | | 9 | | 115-199 | |
| 0833 | 20 | | GA | | 18-8 | 33-23-13 | D40312P | | 33 | | | T10013 | | HV3 | E | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 34

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3704 | 286N3704 | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | |
| 0833 | 20 | GA | | | 17-9 | 33-23-13 | D40312P | | 33 | | T10013 | HV3 | E | | 115-199 |
| 0834 | 20 | GA | | | 26-4 | 33-23-14 | D40312P | | 34 | | D40314J | 4 | | | 001-099 |
| 0834 | 20 | GA | | | 25-3 | 33-23-14 | D40312P | | 34 | | D40314J | 4 | | | 115-199 |
| 0835 | 22 | GA | | | 6-6 | 33-25-13 | D40312P | | 35 | | SM00055 | | 9 | | 001-099 |
| 0835 | 22 | GA | | | 8-2 | 33-25-13 | D40312P | | 35 | | SM00055 | | 9 | | 115-199 |
| 0836 | 16 | GA | | | 3-1 | 33-23-12 | D40312P | | 36 | | SM00016 | | 9 | | 001-099 |
| 0836 | 16 | GA | | | 2-11 | 33-23-12 | D40312P | | 36 | | SM00016 | | 9 | | 115-199 |
| 0838 | 16 | GA | | | 3-1 | 33-23-12 | D40312P | | 38 | | SM00018 | | 9 | | 001-099 |
| 0838 | 16 | GA | | | 2-11 | 33-23-12 | D40312P | | 38 | | SM00018 | | 9 | | 115-199 |
| 0839 | 16 | GA | | | 3-1 | 35-21-12 | D40312P | | 39 | | SM00019 | | 9 | | 001-099 |
| 0839 | 16 | GA | | | 2-11 | 35-21-12 | D40312P | | 39 | | SM00019 | | 9 | | 115-199 |
| 0840 | 18 | GA | | | 3-1 | 35-21-12 | D40312P | | 40 | | SM00020 | | 9 | | 001-099 |
| 0840 | 18 | GA | | | 2-11 | 35-21-12 | D40312P | | 40 | | SM00020 | | 9 | | 115-199 |
| 0842 | 14 | GA | | | 6-0 | 33-23-13 | T10013 | GND | E | | GD03245 | AC.. | E | | 001-099 |
| 0842 | 14 | GA | | | 4-10 | 33-23-13 | T10013 | GND | E | | GD03245 | AC.. | E | | 115-199 |
| 0846 | 16 | GA | | | 6-11 | 33-23-13 | T10013 | | E | | SM00076 | | 9 | | 001-099 |
| 0846 | 16 | GA | | | 4-10 | 33-23-13 | T10013 | LV | E | | SM00076 | | 9 | | 115-199 |
| 0911 | 20 | GA | | | 26-4 | SPARE | D40312P | | 11 | | D40314J | 11 | | | 001-099 |
| 0911 | 20 | GA | | | 25-3 | SPARE | D40312P | | 10 | | D40314J | 11 | | | 115-199 |
| 0912 | 16 | GA | | | 5-3 | 33-23-12 | SM00018 | | 9 | | GD03239 | AC.. | E | | 001-099 |
| 0912 | 16 | GA | | | 6-10 | 33-23-12 | SM00018 | | 9 | | GD03239 | AC.. | E | | 115-199 |
| 0919 | 22 | GA | | | 2-11 | 33-25-12 | D40312P | | 11 | | SM06019 | | 9 | | 115-199 |
| 0921 | 16 | GA | | | 4-1 | 33-23-13 | SM00058 | | 9 | | GD03297 | AC.. | E | | 001-099 |
| 0921 | 16 | GA | | | 2-5 | 33-23-13 | SM00058 | | 9 | | GD03297 | AC.. | E | | 115-199 |
| 0922 | 16 | GA | | | 4-10 | 33-23-13 | SM00118 | | 9 | | GD03237 | AC.. | E | | 001-099 |
| 0922 | 16 | GA | | | 3-8 | 33-23-13 | SM00118 | | 9 | | GD03237 | AC.. | E | | 115-199 |
| 0928 | 16 | GA | | | 3-10 | 33-23-13 | SM00078 | | 9 | | GD03233 | AC.. | E | | 001-099 |
| 0928 | 16 | GA | | | 2-11 | 33-23-13 | SM00078 | | 9 | | GD03233 | AC.. | E | | 115-199 |
| 0930 | 18 | GA | | | 3-10 | 35-21-13 | SM00080 | | 9 | | GD03243 | DC.. | E | | 001-099 |
| 0930 | 18 | GA | | | 2-11 | 35-21-13 | SM00080 | | 9 | | GD03243 | DC.. | E | | 115-199 |
| 0965 | 22 | GA | | | 25-3 | 33-25-12 | D40312P | | 19 | | D40314J | 19 | | | 115-199 |
| 0990 | 18 | GA | | | 4-9 | 35-21-12 | SM00020 | | 9 | | GD03231 | DC.. | E | | ALL |
| 2011B | 22 | GB | A | | 7-3 | 23-31-22 | D05946 | | 14 | | SM00024 | | 9 | | 001-099 |
| 2011B | 22 | GB | A | | 4-11 | 23-31-22 | D05946 | | 13 | | SM00023 | | 9 | | 115-199 |
| 2011R | 22 | GB | A | | 0-0 | 23-31-22 | D05946 | | 13 | | SM00023 | | 9 | | 001-099 |
| 2011R | 22 | GB | A | | 0-0 | 23-31-22 | D05946 | | 14 | | SM00024 | | 9 | | 115-199 |
| 2021B | 22 | GB | B | | 10-5 | 23-31-22 | D05948 | | 14 | | SM00024 | | 9 | | 001-099 |
| 2021B | 22 | GB | B | | 10-0 | 23-31-22 | D05948 | | 13 | | SM00023 | | 9 | | 115-199 |
| 2021R | 22 | GB | B | | 0-0 | 23-31-22 | D05948 | | 13 | | SM00023 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 35

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3704 | 286N3704 | | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | |
| 2021R | 22 | GB | B | | 0-0 | 23-31-22 | D05948 | 14 | | | SM00024 | | 9 | | 115-199 |
| 2023B | 22 | GB | P | | 4-4 | 23-31-22 | SM00024 | | 9 | | SM00044 | | 9 | | 001-099 |
| 2023B | 22 | GB | P | | 4-1 | 23-31-22 | SM00023 | | 9 | | SM00043 | | 9 | | 115-199 |
| 2023R | 22 | GB | P | | 0-0 | 23-31-22 | SM00023 | | 9 | | SM00043 | | 9 | | 001-099 |
| 2023R | 22 | GB | P | | 0-0 | 23-31-22 | SM00024 | | 9 | | SM00044 | | 9 | | 115-199 |
| 2031B | 22 | GB | C | | 8-7 | 23-31-22 | D05950 | 14 | | | SM00044 | | 9 | | 001-099 |
| 2031B | 22 | GB | C | | 8-7 | 23-31-22 | D05950 | 13 | | | SM00043 | | 9 | | 115-199 |
| 2031R | 22 | GB | C | | 0-0 | 23-31-22 | D05950 | 13 | | | SM00043 | | 9 | | 001-099 |
| 2031R | 22 | GB | C | | 0-0 | 23-31-22 | D05950 | 14 | | | SM00044 | | 9 | | 115-199 |
| 2041B | 22 | GB | D | | 12-3 | 23-31-22 | D05952 | 14 | | | SM00044 | | 9 | | 001-099 |
| 2041B | 22 | GB | D | | 10-10 | 23-31-22 | D05952 | 13 | | | SM00043 | | 9 | | 115-199 |
| 2041R | 22 | GB | D | | 0-0 | 23-31-22 | D05952 | 13 | | | SM00043 | | 9 | | 001-099 |
| 2041R | 22 | GB | D | | 0-0 | 23-31-22 | D05952 | 14 | | | SM00044 | | 9 | | 115-199 |
| 2043B | 22 | GB | Q | | 3-6 | 23-31-22 | SM00044 | | 9 | | SM00064 | | 9 | | 001-099 |
| 2043B | 22 | GB | Q | | 5-2 | 23-31-22 | SM00043 | | 9 | | SM00063 | | 9 | | 115-199 |
| 2043R | 22 | GB | Q | | 0-0 | 23-31-22 | SM00043 | | 9 | | SM00063 | | 9 | | 001-099 |
| 2043R | 22 | GB | Q | | 0-0 | 23-31-22 | SM00044 | | 9 | | SM00064 | | 9 | | 115-199 |
| 2051B | 22 | GB | E | | 12-2 | 23-31-22 | D05954 | 14 | | | SM00064 | | 9 | | 001-099 |
| 2051B | 22 | GB | E | | 8-9 | 23-31-22 | D05954 | 13 | | | SM00063 | | 9 | | 115-199 |
| 2051R | 22 | GB | E | | 0-0 | 23-31-22 | D05954 | 13 | | | SM00063 | | 9 | | 001-099 |
| 2051R | 22 | GB | E | | 0-0 | 23-31-22 | D05954 | 14 | | | SM00064 | | 9 | | 115-199 |
| 2061B | 22 | GB | F | | 13-4 | 23-31-22 | D05956 | 14 | | | SM00064 | | 9 | | 001-099 |
| 2061B | 22 | GB | F | | 9-8 | 23-31-22 | D05956 | 13 | | | SM00063 | | 9 | | 115-199 |
| 2061R | 22 | GB | F | | 0-0 | 23-31-22 | D05956 | 13 | | | SM00063 | | 9 | | 001-099 |
| 2061R | 22 | GB | F | | 0-0 | 23-31-22 | D05956 | 14 | | | SM00064 | | 9 | | 115-199 |
| 2063B | 22 | GB | R | | 10-9 | 23-31-22 | SM00064 | | 9 | | SM00084 | | 9 | | 001-099 |
| 2063B | 22 | GB | R | | 6-4 | 23-31-22 | SM00063 | | 9 | | SM00083 | | 9 | | 115-199 |
| 2063R | 22 | GB | R | | 0-0 | 23-31-22 | SM00063 | | 9 | | SM00083 | | 9 | | 001-099 |
| 2063R | 22 | GB | R | | 0-0 | 23-31-22 | SM00064 | | 9 | | SM00084 | | 9 | | 115-199 |
| 2071B | 22 | GB | G | | 7-11 | 23-31-22 | D05958 | 14 | | | SM00084 | | 9 | | 001-099 |
| 2071B | 22 | GB | G | | 7-1 | 23-31-22 | D05958 | 13 | | | SM00083 | | 9 | | 115-199 |
| 2071R | 22 | GB | G | | 0-0 | 23-31-22 | D05958 | 13 | | | SM00083 | | 9 | | 001-099 |
| 2071R | 22 | GB | G | | 0-0 | 23-31-22 | D05958 | 14 | | | SM00084 | | 9 | | 115-199 |
| 2081B | 22 | GB | H | | 10-10 | 23-31-22 | D05960 | 14 | | | SM00084 | | 9 | | 001-099 |
| 2081B | 22 | GB | H | | 10-1 | 23-31-22 | D05960 | 13 | | | SM00083 | | 9 | | 115-199 |
| 2081R | 22 | GB | H | | 0-0 | 23-31-22 | D05960 | 13 | | | SM00083 | | 9 | | 001-099 |
| 2081R | 22 | GB | H | | 0-0 | 23-31-22 | D05960 | 14 | | | SM00084 | | 9 | | 115-199 |
| 2083B | 22 | GB | S | | 7-8 | 23-31-22 | SM00084 | | 9 | | SM00104 | | 9 | | 001-099 |
| 2083B | 22 | GB | S | | 6-0 | 23-31-22 | SM00083 | | 9 | | SM00103 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 36

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | | To | | | | | |
|------------|-------------|----|-------|--------------------------------------|---------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3704 | 286N3704 | | | PSU HARNESS-LEFT, CENTER (continued) | | | | | | | | | | | | |
| 2083R | 22 | GB | S | | 0-0 | 23-31-22 | SM00083 | | | 9 | | SM00103 | | 9 | | 001-099 |
| 2083R | 22 | GB | S | | 0-0 | 23-31-22 | SM00084 | | | 9 | | SM00104 | | 9 | | 115-199 |
| 2091B | 22 | GB | J | | 9-1 | 23-31-22 | D05962 | | 14 | | | SM00104 | | 9 | | 001-099 |
| 2091B | 22 | GB | J | | 8-3 | 23-31-22 | D05962 | | 13 | | | SM00103 | | 9 | | 115-199 |
| 2091R | 22 | GB | J | | 0-0 | 23-31-22 | D05962 | | 13 | | | SM00103 | | 9 | | 001-099 |
| 2091R | 22 | GB | J | | 0-0 | 23-31-22 | D05962 | | 14 | | | SM00104 | | 9 | | 115-199 |
| 2101B | 22 | GB | K | | 11-2 | 23-31-22 | D05964 | | 14 | | | SM00104 | | 9 | | 001-099 |
| 2101B | 22 | GB | K | | 10-4 | 23-31-22 | D05964 | | 13 | | | SM00103 | | 9 | | 115-199 |
| 2101R | 22 | GB | K | | 0-0 | 23-31-22 | D05964 | | 13 | | | SM00103 | | 9 | | 001-099 |
| 2101R | 22 | GB | K | | 0-0 | 23-31-22 | D05964 | | 14 | | | SM00104 | | 9 | | 115-199 |
| 2103B | 22 | GB | T | | 7-10 | 23-31-22 | SM00104 | | | 9 | | SM00124 | | 9 | | 001-099 |
| 2103B | 22 | GB | T | | 5-5 | 23-31-22 | SM00103 | | | 9 | | SM00123 | | 9 | | 115-199 |
| 2103R | 22 | GB | T | | 0-0 | 23-31-22 | SM00103 | | | 9 | | SM00123 | | 9 | | 001-099 |
| 2103R | 22 | GB | T | | 0-0 | 23-31-22 | SM00104 | | | 9 | | SM00124 | | 9 | | 115-199 |
| 2111B | 22 | GB | L | | 9-6 | 23-31-22 | D05966 | | 14 | | | SM00124 | | 9 | | 001-099 |
| 2111B | 22 | GB | L | | 8-3 | 23-31-22 | D05966 | | 13 | | | SM00123 | | 9 | | 115-199 |
| 2111R | 22 | GB | L | | 0-0 | 23-31-22 | D05966 | | 13 | | | SM00123 | | 9 | | 001-099 |
| 2111R | 22 | GB | L | | 0-0 | 23-31-22 | D05966 | | 14 | | | SM00124 | | 9 | | 115-199 |
| 2413B | 22 | GB | M | | 4-9 | 23-31-22 | D40314J | | 14 | | | SM00124 | | 9 | | 001-099 |
| 2413B | 22 | GB | M | | 2-6 | 23-31-22 | D40314J | | 13 | | | SM00123 | | 9 | | 115-199 |
| 2413R | 22 | GB | M | | 0-0 | 23-31-22 | D40314J | | 13 | | | SM00123 | | 9 | | 001-099 |
| 2413R | 22 | GB | M | | 0-0 | 23-31-22 | D40314J | | 14 | | | SM00124 | | 9 | | 115-199 |
| 2423B | 22 | GB | N | | 3-1 | 23-31-22 | D40312P | | 14 | | | SM00024 | | 9 | | 001-099 |
| 2423B | 22 | GB | N | | 2-11 | 23-31-22 | D40312P | | 13 | | | SM00023 | | 9 | | 115-199 |
| 2423R | 22 | GB | N | | 0-0 | 23-31-22 | D40312P | | 13 | | | SM00023 | | 9 | | 001-099 |
| 2423R | 22 | GB | N | | 0-0 | 23-31-22 | D40312P | | 14 | | | SM00024 | | 9 | | 115-199 |
| 6019AD | 22 | GA | | | 4-11 | 33-25-12 | D05946 | | | 9 | | SM06019 | | 9 | | 115-199 |
| 6029AD | 22 | GA | | | 10-0 | 33-25-12 | D05948 | | | 9 | | SM06019 | | 9 | | 115-199 |
| 6039AD | 22 | GA | | | 10-1 | 33-25-12 | D05950 | | | 9 | | SM06039 | | 9 | | 115-199 |
| 6049AD | 22 | GA | | | 12-5 | 33-25-12 | D05952 | | | 9 | | SM06039 | | 9 | | 115-199 |
| 6519AD | 22 | GA | | | 6-11 | 33-25-12 | SM06019 | | | 9 | | SM06039 | | 9 | | 115-199 |
| W3706 | 286N3706 | | | PSU HARNESS-LEFT, AFT | | | | | | | | | | | | |
| 0011G | 16 | GA | | | 7-9 | 33-24-14 | D05968 | | 1 | | | SM00011 | | 9 | | 001-099 |
| 0011G | 16 | GA | | | 8-2 | 33-24-14 | D05968 | | 1 | | | SM00011 | | 9 | | 115-199 |
| 0012WV | 22 | GA | | | 7-9 | 33-25-14 | D05968 | | 2 | | | SM00012 | | 9 | | 001-099 |
| 0012WV | 22 | GA | | | 8-2 | 33-25-14 | D05968 | | 2 | | | SM00012 | | 9 | | 115-199 |
| 0013WG | 22 | GA | | | 7-9 | 33-25-14 | D05968 | | 3 | | | SM00013 | | 9 | | 001-099 |
| 0013WG | 22 | GA | | | 8-2 | 33-25-14 | D05968 | | 3 | | | SM00013 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 37

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | |
| 0015V | 22 | | GA | | 7-9 | 33-25-14 | | D05968 | | 5 | | SM00015 | | 9 | | 001-099 |
| 0015V | 22 | | GA | | 8-2 | 33-25-14 | | D05968 | | 5 | | SM00015 | | 9 | | 115-199 |
| 0016WN | 16 | | GA | | 7-9 | 33-23-13 | | D05968 | | 6 | | SM00016 | | 9 | | 001-099 |
| 0016WN | 16 | | GA | | 8-2 | 33-23-13 | | D05968 | | 6 | | SM00016 | | 9 | | 115-199 |
| 0017W | 20 | | GA | | 7-9 | 33-24-14 | | D05968 | | 7 | | SM00017 | | 9 | | 001-099 |
| 0017W | 20 | | GA | | 8-2 | 33-24-14 | | D05968 | | 7 | | SM00017 | | 9 | | 115-199 |
| 0018WP | 16 | | GA | | 7-9 | 33-23-13 | | D05968 | | 8 | | SM00018 | | 9 | | 001-099 |
| 0018WP | 16 | | GA | | 8-2 | 33-23-13 | | D05968 | | 8 | | SM00018 | | 9 | | 115-199 |
| 0019AJ | 20 | | GA | | 7-9 | 35-21-13 | | D05968 | | 11 | | SM00019 | | 9 | | 001-099 |
| 0019AJ | 20 | | GA | | 8-2 | 35-21-13 | | D05968 | | 11 | | SM00019 | | 9 | | 115-199 |
| 0020K | 18 | | GA | | 7-9 | 35-21-13 | | D05968 | | 10 | | SM00020 | | 9 | | 001-099 |
| 0020K | 18 | | GA | | 8-2 | 35-21-13 | | D05968 | | 10 | | SM00020 | | 9 | | 115-199 |
| 0021G | 16 | | GA | | 8-3 | 33-24-14 | | D05970 | | 1 | | SM00011 | | 9 | | 001-099 |
| 0021G | 16 | | GA | | 8-9 | 33-24-14 | | D05970 | | 1 | | SM00011 | | 9 | | 115-199 |
| 0022WV | 22 | | GA | | 8-3 | 33-25-14 | | D05970 | | 2 | | SM00012 | | 9 | | 001-099 |
| 0022WV | 22 | | GA | | 8-9 | 33-25-14 | | D05970 | | 2 | | SM00012 | | 9 | | 115-199 |
| 0023WG | 22 | | GA | | 8-3 | 33-25-14 | | D05970 | | 3 | | SM00013 | | 9 | | 001-099 |
| 0023WG | 22 | | GA | | 8-9 | 33-25-14 | | D05970 | | 3 | | SM00013 | | 9 | | 115-199 |
| 0025V | 22 | | GA | | 8-3 | 33-25-14 | | D05970 | | 5 | | SM00015 | | 9 | | 001-099 |
| 0025V | 22 | | GA | | 8-9 | 33-25-14 | | D05970 | | 5 | | SM00015 | | 9 | | 115-199 |
| 0026WN | 16 | | GA | | 8-3 | 33-23-13 | | D05970 | | 6 | | SM00016 | | 9 | | 001-099 |
| 0026WN | 16 | | GA | | 8-9 | 33-23-13 | | D05970 | | 6 | | SM00016 | | 9 | | 115-199 |
| 0027W | 20 | | GA | | 8-3 | 33-24-14 | | D05970 | | 7 | | SM00017 | | 9 | | 001-099 |
| 0027W | 20 | | GA | | 8-9 | 33-24-14 | | D05970 | | 7 | | SM00017 | | 9 | | 115-199 |
| 0028WP | 16 | | GA | | 8-3 | 33-23-13 | | D05970 | | 8 | | SM00018 | | 9 | | 001-099 |
| 0028WP | 16 | | GA | | 8-9 | 33-23-13 | | D05970 | | 8 | | SM00018 | | 9 | | 115-199 |
| 0029AJ | 20 | | GA | | 8-3 | 35-21-13 | | D05970 | | 11 | | SM00019 | | 9 | | 001-099 |
| 0029AJ | 20 | | GA | | 8-9 | 35-21-13 | | D05970 | | 11 | | SM00019 | | 9 | | 115-199 |
| 0030K | 18 | | GA | | 8-3 | 35-21-13 | | D05970 | | 10 | | SM00020 | | 9 | | 001-099 |
| 0030K | 18 | | GA | | 8-9 | 35-21-13 | | D05970 | | 10 | | SM00020 | | 9 | | 115-199 |
| 0031G | 16 | | GA | | 8-6 | 33-24-14 | | D05972 | | 1 | | SM00031 | | 9 | | 001-099 |
| 0031G | 16 | | GA | | 9-0 | 33-24-14 | | D05972 | | 1 | | SM00031 | | 9 | | 115-199 |
| 0032WV | 22 | | GA | | 8-6 | 33-25-14 | | D05972 | | 2 | | SM00032 | | 9 | | 001-099 |
| 0032WV | 22 | | GA | | 9-0 | 33-25-14 | | D05972 | | 2 | | SM00032 | | 9 | | 115-199 |
| 0033WG | 22 | | GA | | 8-6 | 33-25-14 | | D05972 | | 3 | | SM00033 | | 9 | | 001-099 |
| 0033WG | 22 | | GA | | 9-0 | 33-25-14 | | D05972 | | 3 | | SM00033 | | 9 | | 115-199 |
| 0035V | 22 | | GA | | 8-6 | 33-25-14 | | D05972 | | 5 | | SM00035 | | 9 | | 001-099 |
| 0035V | 22 | | GA | | 9-0 | 33-25-14 | | D05972 | | 5 | | SM00035 | | 9 | | 115-199 |
| 0036WN | 16 | | GA | | 8-6 | 33-23-13 | | D05972 | | 6 | | SM00036 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 38

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | |
| 0036WN | 16 | GA | | | 9-0 | 33-23-13 | D05972 | 6 | | | SM00036 | 9 | | | 115-199 |
| 0037W | 20 | GA | | | 8-6 | 33-24-14 | D05972 | 7 | | | SM00037 | 9 | | | 001-099 |
| 0037W | 20 | GA | | | 9-0 | 33-24-14 | D05972 | 7 | | | SM00037 | 9 | | | 115-199 |
| 0038WP | 16 | GA | | | 8-6 | 33-23-13 | D05972 | 8 | | | SM00038 | 9 | | | 001-099 |
| 0038WP | 16 | GA | | | 9-0 | 33-23-13 | D05972 | 8 | | | SM00038 | 9 | | | 115-199 |
| 0039AJ | 20 | GA | | | 8-6 | 35-21-13 | D05972 | 11 | | | SM00039 | 9 | | | 001-099 |
| 0039AJ | 20 | GA | | | 9-0 | 35-21-13 | D05972 | 11 | | | SM00039 | 9 | | | 115-199 |
| 0040K | 18 | GA | | | 8-6 | 35-21-13 | D05972 | 10 | | | SM00040 | 9 | | | 001-099 |
| 0040K | 18 | GA | | | 9-0 | 35-21-13 | D05972 | 10 | | | SM00040 | 9 | | | 115-199 |
| 0041G | 16 | GA | | | 7-4 | 33-24-14 | D05974 | 1 | | | SM00031 | 9 | | | 001-099 |
| 0041G | 16 | GA | | | 7-9 | 33-24-14 | D05974 | 1 | | | SM00031 | 9 | | | 115-199 |
| 0042WV | 22 | GA | | | 7-4 | 33-25-14 | D05974 | 2 | | | SM00032 | 9 | | | 001-099 |
| 0042WV | 22 | GA | | | 7-9 | 33-25-14 | D05974 | 2 | | | SM00032 | 9 | | | 115-199 |
| 0043WG | 22 | GA | | | 7-4 | 33-25-14 | D05974 | 3 | | | SM00033 | 9 | | | 001-099 |
| 0043WG | 22 | GA | | | 7-9 | 33-25-14 | D05974 | 3 | | | SM00033 | 9 | | | 115-199 |
| 0045V | 22 | GA | | | 7-4 | 33-25-14 | D05974 | 5 | | | SM00035 | 9 | | | 001-099 |
| 0045V | 22 | GA | | | 7-9 | 33-25-14 | D05974 | 5 | | | SM00035 | 9 | | | 115-199 |
| 0046WN | 16 | GA | | | 7-4 | 33-23-13 | D05974 | 6 | | | SM00036 | 9 | | | 001-099 |
| 0046WN | 16 | GA | | | 7-9 | 33-23-13 | D05974 | 6 | | | SM00036 | 9 | | | 115-199 |
| 0047W | 20 | GA | | | 7-4 | 33-24-14 | D05974 | 7 | | | SM00037 | 9 | | | 001-099 |
| 0047W | 20 | GA | | | 7-9 | 33-24-14 | D05974 | 7 | | | SM00037 | 9 | | | 115-199 |
| 0048WP | 16 | GA | | | 7-4 | 33-23-13 | D05974 | 8 | | | SM00038 | 9 | | | 001-099 |
| 0048WP | 16 | GA | | | 7-9 | 33-23-13 | D05974 | 8 | | | SM00038 | 9 | | | 115-199 |
| 0049AJ | 20 | GA | | | 7-4 | 35-21-13 | D05974 | 11 | | | SM00039 | 9 | | | 001-099 |
| 0049AJ | 20 | GA | | | 7-9 | 35-21-13 | D05974 | 11 | | | SM00039 | 9 | | | 115-199 |
| 0050K | 18 | GA | | | 7-4 | 35-21-13 | D05974 | 10 | | | SM00040 | 9 | | | 001-099 |
| 0050K | 18 | GA | | | 7-9 | 35-21-13 | D05974 | 10 | | | SM00040 | 9 | | | 115-199 |
| 0051G | 16 | GA | | | 9-5 | 33-24-14 | D05976 | 1 | | | SM00051 | 9 | | | ALL |
| 0052WV | 22 | GA | | | 9-5 | 33-25-14 | D05976 | 2 | | | SM00052 | 9 | | | ALL |
| 0053WG | 22 | GA | | | 9-5 | 33-25-14 | D05976 | 3 | | | SM00053 | 9 | | | ALL |
| 0055V | 22 | GA | | | 9-5 | 33-25-14 | D05976 | 5 | | | SM00055 | 9 | | | ALL |
| 0056WN | 16 | GA | | | 9-5 | 33-23-14 | D05976 | 6 | | | SM00056 | 9 | | | ALL |
| 0057W | 20 | GA | | | 9-5 | 33-24-14 | D05976 | 7 | | | SM00057 | 9 | | | ALL |
| 0058WP | 16 | GA | | | 9-5 | 33-23-14 | D05976 | 8 | | | SM00058 | 9 | | | ALL |
| 0059AJ | 20 | GA | | | 9-5 | 35-21-13 | D05976 | 11 | | | SM00059 | 9 | | | ALL |
| 0060K | 18 | GA | | | 9-5 | 35-21-13 | D05976 | 10 | | | SM00060 | 9 | | | ALL |
| 0061G | 16 | GA | | | 8-5 | 33-24-14 | D05978 | 1 | | | SM00051 | 9 | | | 001-099 |
| 0061G | 16 | GA | | | 9-0 | 33-24-14 | D05978 | 1 | | | SM00051 | 9 | | | 115-199 |
| 0062WV | 22 | GA | | | 8-5 | 33-25-14 | D05978 | 2 | | | SM00052 | 9 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 39

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|-------|-----|-----------------------------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|--|--|
| | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3706 | 286N3706 | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | | |
| 0062WV | 22 | GA | | 9-0 | 33-25-14 | D05978 | | | 2 | | | SM00052 | 9 | 115-199 | | |
| 0063WG | 22 | GA | | 8-5 | 33-25-14 | D05978 | | | 3 | | | SM00053 | 9 | 001-099 | | |
| 0063WG | 22 | GA | | 9-0 | 33-25-14 | D05978 | | | 3 | | | SM00053 | 9 | 115-199 | | |
| 0065V | 22 | GA | | 8-5 | 33-25-14 | D05978 | | | 5 | | | SM00055 | 9 | 001-099 | | |
| 0065V | 22 | GA | | 9-0 | 33-25-14 | D05978 | | | 5 | | | SM00055 | 9 | 115-199 | | |
| 0066WN | 16 | GA | | 8-5 | 33-23-14 | D05978 | | | 6 | | | SM00056 | 9 | 001-099 | | |
| 0066WN | 16 | GA | | 9-0 | 33-23-14 | D05978 | | | 6 | | | SM00056 | 9 | 115-199 | | |
| 0067W | 20 | GA | | 8-5 | 33-24-14 | D05978 | | | 7 | | | SM00057 | 9 | 001-099 | | |
| 0067W | 20 | GA | | 9-0 | 33-24-14 | D05978 | | | 7 | | | SM00057 | 9 | 115-199 | | |
| 0068WP | 16 | GA | | 8-5 | 33-23-14 | D05978 | | | 8 | | | SM00058 | 9 | 001-099 | | |
| 0068WP | 16 | GA | | 9-0 | 33-23-14 | D05978 | | | 8 | | | SM00058 | 9 | 115-199 | | |
| 0069AJ | 20 | GA | | 8-5 | 35-21-13 | D05978 | | | 11 | | | SM00059 | 9 | 001-099 | | |
| 0069AJ | 20 | GA | | 9-0 | 35-21-13 | D05978 | | | 11 | | | SM00059 | 9 | 115-199 | | |
| 0070K | 18 | GA | | 8-5 | 35-21-13 | D05978 | | | 10 | | | SM00060 | 9 | 001-099 | | |
| 0070K | 18 | GA | | 9-0 | 35-21-13 | D05978 | | | 10 | | | SM00060 | 9 | 115-199 | | |
| 0071G | 16 | GA | | 8-5 | 33-24-14 | D05980 | | | 1 | | | SM00071 | 9 | 001-099 | | |
| 0071G | 16 | GA | | 8-8 | 33-24-14 | D05980 | | | 1 | | | SM00071 | 9 | 115-199 | | |
| 0072WV | 22 | GA | | 8-5 | 33-25-14 | D05980 | | | 2 | | | SM00072 | 9 | 001-099 | | |
| 0072WV | 22 | GA | | 8-8 | 33-25-14 | D05980 | | | 2 | | | SM00072 | 9 | 115-199 | | |
| 0073WG | 22 | GA | | 8-5 | 33-25-14 | D05980 | | | 3 | | | SM00073 | 9 | 001-099 | | |
| 0073WG | 22 | GA | | 8-8 | 33-25-14 | D05980 | | | 3 | | | SM00073 | 9 | 115-199 | | |
| 0075V | 22 | GA | | 8-5 | 33-25-14 | D05980 | | | 5 | | | SM00075 | 9 | 001-099 | | |
| 0075V | 22 | GA | | 8-8 | 33-25-14 | D05980 | | | 5 | | | SM00075 | 9 | 115-199 | | |
| 0076WN | 16 | GA | | 8-5 | 33-23-14 | D05980 | | | 6 | | | SM00076 | 9 | 001-099 | | |
| 0076WN | 16 | GA | | 8-8 | 33-23-14 | D05980 | | | 6 | | | SM00076 | 9 | 115-199 | | |
| 0077W | 20 | GA | | 8-5 | 33-24-14 | D05980 | | | 7 | | | SM00077 | 9 | 001-099 | | |
| 0077W | 20 | GA | | 8-8 | 33-24-14 | D05980 | | | 7 | | | SM00077 | 9 | 115-199 | | |
| 0078WP | 16 | GA | | 8-5 | 33-23-14 | D05980 | | | 8 | | | SM00078 | 9 | 001-099 | | |
| 0078WP | 16 | GA | | 8-8 | 33-23-14 | D05980 | | | 8 | | | SM00078 | 9 | 115-199 | | |
| 0079AJ | 20 | GA | | 8-5 | 35-21-13 | D05980 | | | 11 | | | SM00079 | 9 | 001-099 | | |
| 0079AJ | 20 | GA | | 8-8 | 35-21-13 | D05980 | | | 11 | | | SM00079 | 9 | 115-199 | | |
| 0080K | 18 | GA | | 8-5 | 35-21-13 | D05980 | | | 10 | | | SM00080 | 9 | 001-099 | | |
| 0080K | 18 | GA | | 8-8 | 35-21-13 | D05980 | | | 10 | | | SM00080 | 9 | 115-199 | | |
| 0081G | 16 | GA | | 10-3 | 33-24-14 | D05982 | | | 1 | | | SM00071 | 9 | 001-099 | | |
| 0081G | 16 | GA | | 10-6 | 33-24-14 | D05982 | | | 1 | | | SM00071 | 9 | 115-199 | | |
| 0082WV | 22 | GA | | 10-3 | 33-25-14 | D05982 | | | 2 | | | SM00072 | 9 | 001-099 | | |
| 0082WV | 22 | GA | | 10-6 | 33-25-14 | D05982 | | | 2 | | | SM00072 | 9 | 115-199 | | |
| 0083WG | 22 | GA | | 10-3 | 33-25-14 | D05982 | | | 3 | | | SM00073 | 9 | 001-099 | | |
| 0083WG | 22 | GA | | 10-6 | 33-25-14 | D05982 | | | 3 | | | SM00073 | 9 | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 40

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | |
| 0085V | 22 | GA | | | 10-3 | 33-25-14 | D05982 | | 5 | | SM00075 | | 9 | | 001-099 |
| 0085V | 22 | GA | | | 10-6 | 33-25-14 | D05982 | | 5 | | SM00075 | | 9 | | 115-199 |
| 0086WN | 16 | GA | | | 10-3 | 33-23-14 | D05982 | | 6 | | SM00076 | | 9 | | 001-099 |
| 0086WN | 16 | GA | | | 10-6 | 33-23-14 | D05982 | | 6 | | SM00076 | | 9 | | 115-199 |
| 0087W | 20 | GA | | | 10-3 | 33-24-14 | D05982 | | 7 | | SM00077 | | 9 | | 001-099 |
| 0087W | 20 | GA | | | 10-6 | 33-24-14 | D05982 | | 7 | | SM00077 | | 9 | | 115-199 |
| 0088WP | 16 | GA | | | 10-3 | 33-23-14 | D05982 | | 8 | | SM00078 | | 9 | | 001-099 |
| 0088WP | 16 | GA | | | 10-6 | 33-23-14 | D05982 | | 8 | | SM00078 | | 9 | | 115-199 |
| 0089AJ | 20 | GA | | | 10-3 | 35-21-13 | D05982 | | 11 | | SM00079 | | 9 | | 001-099 |
| 0089AJ | 20 | GA | | | 10-6 | 35-21-13 | D05982 | | 11 | | SM00079 | | 9 | | 115-199 |
| 0090K | 18 | GA | | | 10-3 | 35-21-13 | D05982 | | 10 | | SM00080 | | 9 | | 001-099 |
| 0090K | 18 | GA | | | 10-6 | 35-21-13 | D05982 | | 10 | | SM00080 | | 9 | | 115-199 |
| 0091G | 16 | GA | | | 7-6 | 33-24-14 | D05984 | | 1 | | SM00091 | | 9 | | 001-099 |
| 0091G | 16 | GA | | | 7-10 | 33-24-14 | D05984 | | 1 | | SM00091 | | 9 | | 115-199 |
| 0092WV | 22 | GA | | | 7-6 | 33-25-14 | D05984 | | 2 | | SM00092 | | 9 | | 001-099 |
| 0092WV | 22 | GA | | | 7-10 | 33-25-14 | D05984 | | 2 | | SM00092 | | 9 | | 115-199 |
| 0093WG | 22 | GA | | | 7-6 | 33-25-14 | D05984 | | 3 | | SM00093 | | 9 | | 001-099 |
| 0093WG | 22 | GA | | | 7-10 | 33-25-14 | D05984 | | 3 | | SM00093 | | 9 | | 115-199 |
| 0095V | 22 | GA | | | 7-6 | 33-25-14 | D05984 | | 5 | | SM00095 | | 9 | | 001-099 |
| 0095V | 22 | GA | | | 7-10 | 33-25-14 | D05984 | | 5 | | SM00095 | | 9 | | 115-199 |
| 0096WN | 16 | GA | | | 7-6 | 33-23-14 | D05984 | | 6 | | SM00096 | | 9 | | 001-099 |
| 0096WN | 16 | GA | | | 7-10 | 33-23-14 | D05984 | | 6 | | SM00096 | | 9 | | 115-199 |
| 0097W | 20 | GA | | | 7-6 | 33-24-14 | D05984 | | 7 | | SM00097 | | 9 | | 001-099 |
| 0097W | 20 | GA | | | 7-10 | 33-24-14 | D05984 | | 7 | | SM00097 | | 9 | | 115-199 |
| 0098WP | 16 | GA | | | 7-6 | 33-23-14 | D05984 | | 8 | | SM00098 | | 9 | | 001-099 |
| 0098WP | 16 | GA | | | 7-10 | 33-23-14 | D05984 | | 8 | | SM00098 | | 9 | | 115-199 |
| 0099AJ | 20 | GA | | | 7-6 | 35-21-13 | D05984 | | 11 | | SM00099 | | 9 | | 001-099 |
| 0099AJ | 20 | GA | | | 7-10 | 35-21-13 | D05984 | | 11 | | SM00099 | | 9 | | 115-199 |
| 0100K | 18 | GA | | | 7-6 | 35-21-13 | D05984 | | 10 | | SM00100 | | 9 | | 001-099 |
| 0100K | 18 | GA | | | 7-10 | 35-21-13 | D05984 | | 10 | | SM00100 | | 9 | | 115-199 |
| 0101G | 16 | GA | | | 8-8 | 33-24-14 | D05986 | | 1 | | SM00091 | | 9 | | 001-099 |
| 0101G | 16 | GA | | | 9-0 | 33-24-14 | D05986 | | 1 | | SM00091 | | 9 | | 115-199 |
| 0102WV | 22 | GA | | | 8-8 | 33-25-14 | D05986 | | 2 | | SM00092 | | 9 | | 001-099 |
| 0102WV | 22 | GA | | | 9-0 | 33-25-14 | D05986 | | 2 | | SM00092 | | 9 | | 115-199 |
| 0103WG | 22 | GA | | | 8-8 | 33-25-14 | D05986 | | 3 | | SM00093 | | 9 | | 001-099 |
| 0103WG | 22 | GA | | | 9-0 | 33-25-14 | D05986 | | 3 | | SM00093 | | 9 | | 115-199 |
| 0105V | 22 | GA | | | 8-8 | 33-25-14 | D05986 | | 5 | | SM00095 | | 9 | | 001-099 |
| 0105V | 22 | GA | | | 9-0 | 33-25-14 | D05986 | | 5 | | SM00095 | | 9 | | 115-199 |
| 0106WN | 16 | GA | | | 8-8 | 33-23-14 | D05986 | | 6 | | SM00096 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 41

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | |
| 0106WN | 16 | | GA | | 9-0 | 33-23-14 | | D05986 | | 6 | | SM00096 | | 9 | | 115-199 |
| 0107W | 20 | | GA | | 8-8 | 33-24-14 | | D05986 | | 7 | | SM00097 | | 9 | | 001-099 |
| 0107W | 20 | | GA | | 9-0 | 33-24-14 | | D05986 | | 7 | | SM00097 | | 9 | | 115-199 |
| 0108WP | 16 | | GA | | 8-8 | 33-23-14 | | D05986 | | 8 | | SM00098 | | 9 | | 001-099 |
| 0108WP | 16 | | GA | | 9-0 | 33-23-14 | | D05986 | | 8 | | SM00098 | | 9 | | 115-199 |
| 0109AJ | 20 | | GA | | 8-8 | 35-21-13 | | D05986 | | 11 | | SM00099 | | 9 | | 001-099 |
| 0109AJ | 20 | | GA | | 9-0 | 35-21-13 | | D05986 | | 11 | | SM00099 | | 9 | | 115-199 |
| 0110K | 18 | | GA | | 8-8 | 35-21-13 | | D05986 | | 10 | | SM00100 | | 9 | | 001-099 |
| 0110K | 18 | | GA | | 9-0 | 35-21-13 | | D05986 | | 10 | | SM00100 | | 9 | | 115-199 |
| 0111G | 16 | | GA | | 9-4 | 33-24-14 | | D05988 | | 1 | | SM00111 | | 9 | | 001-099 |
| 0111G | 16 | | GA | | 10-1 | 33-24-14 | | D05988 | | 1 | | SM00111 | | 9 | | 115-199 |
| 0112WV | 22 | | GA | | 9-4 | 33-25-14 | | D05988 | | 2 | | SM00112 | | 9 | | 001-099 |
| 0112WV | 22 | | GA | | 10-1 | 33-25-14 | | D05988 | | 2 | | SM00112 | | 9 | | 115-199 |
| 0113WG | 22 | | GA | | 9-4 | 33-25-14 | | D05988 | | 3 | | SM00113 | | 9 | | 001-099 |
| 0113WG | 22 | | GA | | 10-1 | 33-25-14 | | D05988 | | 3 | | SM00113 | | 9 | | 115-199 |
| 0115V | 22 | | GA | | 9-4 | 33-25-14 | | D05988 | | 5 | | SM00115 | | 9 | | 001-099 |
| 0115V | 22 | | GA | | 10-1 | 33-25-14 | | D05988 | | 5 | | SM00115 | | 9 | | 115-199 |
| 0116WN | 16 | | GA | | 9-4 | 33-23-14 | | D05988 | | 6 | | SM00116 | | 9 | | 001-099 |
| 0116WN | 16 | | GA | | 10-1 | 33-23-14 | | D05988 | | 6 | | SM00116 | | 9 | | 115-199 |
| 0117W | 20 | | GA | | 9-4 | 33-24-14 | | D05988 | | 7 | | SM00117 | | 9 | | 001-099 |
| 0117W | 20 | | GA | | 10-1 | 33-24-14 | | D05988 | | 7 | | SM00117 | | 9 | | 115-199 |
| 0118WP | 16 | | GA | | 9-4 | 33-23-14 | | D05988 | | 8 | | SM00118 | | 9 | | 001-099 |
| 0118WP | 16 | | GA | | 10-1 | 33-23-14 | | D05988 | | 8 | | SM00118 | | 9 | | 115-199 |
| 0119AJ | 20 | | GA | | 9-4 | 35-21-13 | | D05988 | | 11 | | SM00119 | | 9 | | 001-099 |
| 0119AJ | 20 | | GA | | 10-1 | 35-21-13 | | D05988 | | 11 | | SM00119 | | 9 | | 115-199 |
| 0120K | 18 | | GA | | 9-4 | 35-21-13 | | D05988 | | 10 | | SM00120 | | 9 | | 001-099 |
| 0120K | 18 | | GA | | 10-1 | 35-21-13 | | D05988 | | 10 | | SM00120 | | 9 | | 115-199 |
| 0121G | 16 | | GA | | 8-7 | 33-24-14 | | D05990 | | 1 | | SM00111 | | 9 | | 001-099 |
| 0121G | 16 | | GA | | 8-10 | 33-24-14 | | D05990 | | 1 | | SM00111 | | 9 | | 115-199 |
| 0122WV | 22 | | GA | | 8-7 | 33-25-14 | | D05990 | | 2 | | SM00112 | | 9 | | 001-099 |
| 0122WV | 22 | | GA | | 8-10 | 33-25-14 | | D05990 | | 2 | | SM00112 | | 9 | | 115-199 |
| 0123WG | 22 | | GA | | 8-7 | 33-25-14 | | D05990 | | 3 | | SM00113 | | 9 | | 001-099 |
| 0123WG | 22 | | GA | | 8-10 | 33-25-14 | | D05990 | | 3 | | SM00113 | | 9 | | 115-199 |
| 0125V | 22 | | GA | | 8-7 | 33-25-14 | | D05990 | | 5 | | SM00115 | | 9 | | 001-099 |
| 0125V | 22 | | GA | | 8-10 | 33-25-14 | | D05990 | | 5 | | SM00115 | | 9 | | 115-199 |
| 0126WN | 16 | | GA | | 8-7 | 33-23-14 | | D05990 | | 6 | | SM00116 | | 9 | | 001-099 |
| 0126WN | 16 | | GA | | 8-10 | 33-23-14 | | D05990 | | 6 | | SM00116 | | 9 | | 115-199 |
| 0127W | 20 | | GA | | 8-7 | 33-24-14 | | D05990 | | 7 | | SM00117 | | 9 | | 001-099 |
| 0127W | 20 | | GA | | 8-10 | 33-24-14 | | D05990 | | 7 | | SM00117 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 42

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | |
| 0128WP | 16 | GA | | | 8-7 | 33-23-14 | D05990 | | | | SM00118 | | | 9 | 001-099 |
| 0128WP | 16 | GA | | | 8-10 | 33-23-14 | D05990 | | | | SM00118 | | | 9 | 115-199 |
| 0129AJ | 20 | GA | | | 8-7 | 35-21-13 | D05990 | | | | SM00119 | | | 9 | 001-099 |
| 0129AJ | 20 | GA | | | 8-10 | 35-21-13 | D05990 | | | | SM00119 | | | 9 | 115-199 |
| 0130K | 18 | GA | | | 8-7 | 35-21-13 | D05990 | | | | SM00120 | | | 9 | 001-099 |
| 0130K | 18 | GA | | | 8-10 | 35-21-13 | D05990 | | | | SM00120 | | | 9 | 115-199 |
| 0131G | 16 | GA | | | 9-5 | 33-24-14 | D05992 | | | | SM00131 | | | 9 | 001-099 |
| 0131G | 16 | GA | | | 8-10 | 33-24-14 | D05992 | | | | SM00131 | | | 9 | 115-199 |
| 0132WV | 22 | GA | | | 9-5 | 33-25-14 | D05992 | | | | SM00132 | | | 9 | 001-099 |
| 0132WV | 22 | GA | | | 8-10 | 33-25-14 | D05992 | | | | SM00132 | | | 9 | 115-199 |
| 0133WG | 22 | GA | | | 9-5 | 33-25-14 | D05992 | | | | SM00133 | | | 9 | 001-099 |
| 0133WG | 22 | GA | | | 8-10 | 33-25-14 | D05992 | | | | SM00133 | | | 9 | 115-199 |
| 0135V | 22 | GA | | | 9-5 | 33-25-14 | D05992 | | | | SM00135 | | | 9 | 001-099 |
| 0135V | 22 | GA | | | 8-10 | 33-25-14 | D05992 | | | | SM00135 | | | 9 | 115-199 |
| 0136WN | 16 | GA | | | 9-5 | 33-23-14 | D05992 | | | | SM00136 | | | 9 | 001-099 |
| 0136WN | 16 | GA | | | 8-10 | 33-23-14 | D05992 | | | | SM00136 | | | 9 | 115-199 |
| 0137W | 20 | GA | | | 9-5 | 33-24-14 | D05992 | | | | SM00137 | | | 9 | 001-099 |
| 0137W | 20 | GA | | | 8-10 | 33-24-14 | D05992 | | | | SM00137 | | | 9 | 115-199 |
| 0138WP | 16 | GA | | | 9-5 | 33-23-14 | D05992 | | | | SM00138 | | | 9 | 001-099 |
| 0138WP | 16 | GA | | | 8-10 | 33-23-14 | D05992 | | | | SM00138 | | | 9 | 115-199 |
| 0139AJ | 20 | GA | | | 9-5 | 35-21-13 | D05992 | | | | SM00139 | | | 9 | 001-099 |
| 0139AJ | 20 | GA | | | 8-10 | 35-21-13 | D05992 | | | | SM00139 | | | 9 | 115-199 |
| 0140K | 18 | GA | | | 9-5 | 35-21-13 | D05992 | | | | SM00140 | | | 9 | 001-099 |
| 0140K | 18 | GA | | | 8-10 | 35-21-13 | D05992 | | | | SM00140 | | | 9 | 115-199 |
| 0141G | 16 | GA | | | 8-3 | 33-24-14 | D05994 | | | | SM00131 | | | 9 | 001-099 |
| 0141G | 16 | GA | | | 8-6 | 33-24-14 | D05994 | | | | SM00131 | | | 9 | 115-199 |
| 0142WV | 22 | GA | | | 8-3 | 33-25-14 | D05994 | | | | SM00132 | | | 9 | 001-099 |
| 0142WV | 22 | GA | | | 8-6 | 33-25-14 | D05994 | | | | SM00132 | | | 9 | 115-199 |
| 0143WG | 22 | GA | | | 8-3 | 33-25-14 | D05994 | | | | SM00133 | | | 9 | 001-099 |
| 0143WG | 22 | GA | | | 8-6 | 33-25-14 | D05994 | | | | SM00133 | | | 9 | 115-199 |
| 0145V | 22 | GA | | | 8-3 | 33-25-14 | D05994 | | | | SM00135 | | | 9 | 001-099 |
| 0145V | 22 | GA | | | 8-6 | 33-25-14 | D05994 | | | | SM00135 | | | 9 | 115-199 |
| 0146WN | 16 | GA | | | 8-3 | 33-23-14 | D05994 | | | | SM00136 | | | 9 | 001-099 |
| 0146WN | 16 | GA | | | 8-6 | 33-23-14 | D05994 | | | | SM00136 | | | 9 | 115-199 |
| 0147W | 20 | GA | | | 8-3 | 33-24-14 | D05994 | | | | SM00137 | | | 9 | 001-099 |
| 0147W | 20 | GA | | | 8-6 | 33-24-14 | D05994 | | | | SM00137 | | | 9 | 115-199 |
| 0148WP | 16 | GA | | | 8-3 | 33-23-14 | D05994 | | | | SM00138 | | | 9 | 001-099 |
| 0148WP | 16 | GA | | | 8-6 | 33-23-14 | D05994 | | | | SM00138 | | | 9 | 115-199 |
| 0149AJ | 20 | GA | | | 8-3 | 35-21-13 | D05994 | | | | SM00139 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 43

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | | |
|------------------------|-------------|----|----|-----|-----------------------------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W3706 | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | | |
| 0149AJ | 20 | | GA | | 8-6 | 35-21-13 | D05994 | | | 11 | | | SM00139 | | 9 | | 115-199 |
| 0150K | 18 | | GA | | 8-3 | 35-21-13 | D05994 | | | 10 | | | SM00140 | | 9 | | 001-099 |
| 0150K | 18 | | GA | | 8-6 | 35-21-13 | D05994 | | | 10 | | | SM00140 | | 9 | | 115-199 |
| 0151G | 16 | | GA | | 5-1 | 33-24-14 | D05996 | | | 1 | | | SM00151 | | 9 | | 001-099 |
| 0151G | 16 | | GA | | 5-4 | 33-24-14 | D05996 | | | 1 | | | SM00151 | | 9 | | 115-199 |
| 0152WV | 22 | | GA | | 5-1 | 33-25-14 | D05996 | | | 2 | | | SM00152 | | 9 | | 001-099 |
| 0152WV | 22 | | GA | | 5-4 | 33-25-14 | D05996 | | | 2 | | | SM00152 | | 9 | | 115-199 |
| 0153WG | 22 | | GA | | 5-1 | 33-25-14 | D05996 | | | 3 | | | SM00153 | | 9 | | 001-099 |
| 0153WG | 22 | | GA | | 5-4 | 33-25-14 | D05996 | | | 3 | | | SM00153 | | 9 | | 115-199 |
| 0155V | 22 | | GA | | 5-1 | 33-25-14 | D05996 | | | 5 | | | SM00155 | | 9 | | 001-099 |
| 0155V | 22 | | GA | | 5-4 | 33-25-14 | D05996 | | | 5 | | | SM00155 | | 9 | | 115-199 |
| 0156WN | 16 | | GA | | 5-1 | 33-23-14 | D05996 | | | 6 | | | SM00156 | | 9 | | 001-099 |
| 0156WN | 16 | | GA | | 5-4 | 33-23-14 | D05996 | | | 6 | | | SM00156 | | 9 | | 115-199 |
| 0157W | 20 | | GA | | 5-1 | 33-24-14 | D05996 | | | 7 | | | SM00157 | | 9 | | 001-099 |
| 0157W | 20 | | GA | | 5-4 | 33-24-14 | D05996 | | | 7 | | | SM00157 | | 9 | | 115-199 |
| 0158WP | 16 | | GA | | 5-1 | 33-23-14 | D05996 | | | 8 | | | SM00158 | | 9 | | 001-099 |
| 0158WP | 16 | | GA | | 5-4 | 33-23-14 | D05996 | | | 8 | | | SM00158 | | 9 | | 115-199 |
| 0159AJ | 20 | | GA | | 5-1 | 35-21-13 | D05996 | | | 11 | | | SM00159 | | 9 | | 001-099 |
| 0159AJ | 20 | | GA | | 5-4 | 35-21-13 | D05996 | | | 11 | | | SM00159 | | 9 | | 115-199 |
| 0160K | 18 | | GA | | 5-1 | 35-21-13 | D05996 | | | 10 | | | SM00160 | | 9 | | 001-099 |
| 0160K | 18 | | GA | | 5-4 | 35-21-13 | D05996 | | | 10 | | | SM00160 | | 9 | | 115-199 |
| 0161G | 16 | | GA | | 4-11 | 33-24-14 | D05998 | | | 1 | | | SM00151 | | 9 | | 001-099 |
| 0161G | 16 | | GA | | 5-3 | 33-24-14 | D05998 | | | 1 | | | SM00151 | | 9 | | 115-199 |
| 0162WV | 22 | | GA | | 4-11 | 33-25-14 | D05998 | | | 2 | | | SM00152 | | 9 | | 001-099 |
| 0162WV | 22 | | GA | | 5-3 | 33-25-14 | D05998 | | | 2 | | | SM00152 | | 9 | | 115-199 |
| 0163WG | 22 | | GA | | 4-11 | 33-25-14 | D05998 | | | 3 | | | SM00153 | | 9 | | 001-099 |
| 0163WG | 22 | | GA | | 5-3 | 33-25-14 | D05998 | | | 3 | | | SM00153 | | 9 | | 115-199 |
| 0165V | 22 | | GA | | 4-11 | 33-25-14 | D05998 | | | 5 | | | SM00155 | | 9 | | 001-099 |
| 0165V | 22 | | GA | | 5-3 | 33-25-14 | D05998 | | | 5 | | | SM00155 | | 9 | | 115-199 |
| 0166WN | 16 | | GA | | 4-11 | 33-23-14 | D05998 | | | 6 | | | SM00156 | | 9 | | 001-099 |
| 0166WN | 16 | | GA | | 5-3 | 33-23-14 | D05998 | | | 6 | | | SM00156 | | 9 | | 115-199 |
| 0167W | 20 | | GA | | 4-11 | 33-24-14 | D05998 | | | 7 | | | SM00157 | | 9 | | 001-099 |
| 0167W | 20 | | GA | | 5-3 | 33-24-14 | D05998 | | | 7 | | | SM00157 | | 9 | | 115-199 |
| 0168WP | 16 | | GA | | 4-11 | 33-23-14 | D05998 | | | 8 | | | SM00158 | | 9 | | 001-099 |
| 0168WP | 16 | | GA | | 5-3 | 33-23-14 | D05998 | | | 8 | | | SM00158 | | 9 | | 115-199 |
| 0169AJ | 20 | | GA | | 4-11 | 35-21-13 | D05998 | | | 11 | | | SM00159 | | 9 | | 001-099 |
| 0169AJ | 20 | | GA | | 5-3 | 35-21-13 | D05998 | | | 11 | | | SM00159 | | 9 | | 115-199 |
| 0170K | 18 | | GA | | 4-11 | 35-21-13 | D05998 | | | 10 | | | SM00160 | | 9 | | 001-099 |
| 0170K | 18 | | GA | | 5-3 | 35-21-13 | D05998 | | | 10 | | | SM00160 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 44

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | |
| 0291G | 16 | | GA | | 8-6 | 33-24-14 | D07348 | | | | SM00051 | | 9 | | 001-099 |
| 0291G | 16 | | GA | | 9-8 | 33-24-14 | D07348 | | | | SM00051 | | 9 | | 115-199 |
| 0292WV | 22 | | GA | | 8-6 | 33-25-14 | D07348 | | | | SM00052 | | 9 | | 001-099 |
| 0292WV | 22 | | GA | | 9-8 | 33-25-14 | D07348 | | | | SM00052 | | 9 | | 115-199 |
| 0293WG | 22 | | GA | | 8-6 | 33-25-14 | D07348 | | | | SM00053 | | 9 | | 001-099 |
| 0293WG | 22 | | GA | | 9-8 | 33-25-14 | D07348 | | | | SM00053 | | 9 | | 115-199 |
| 0295V | 22 | | GA | | 8-6 | 33-25-14 | D07348 | | | | SM00055 | | 9 | | 001-099 |
| 0295V | 22 | | GA | | 9-8 | 33-25-14 | D07348 | | | | SM00055 | | 9 | | 115-199 |
| 0296WN | 16 | | GA | | 8-6 | 33-23-14 | D07348 | | | | SM00056 | | 9 | | 001-099 |
| 0296WN | 16 | | GA | | 9-8 | 33-23-14 | D07348 | | | | SM00056 | | 9 | | 115-199 |
| 0297W | 20 | | GA | | 8-6 | 33-24-14 | D07348 | | | | SM00057 | | 9 | | 001-099 |
| 0297W | 20 | | GA | | 9-8 | 33-24-14 | D07348 | | | | SM00057 | | 9 | | 115-199 |
| 0298WP | 16 | | GA | | 8-6 | 33-23-14 | D07348 | | | | SM00058 | | 9 | | 001-099 |
| 0298WP | 16 | | GA | | 9-8 | 33-23-14 | D07348 | | | | SM00058 | | 9 | | 115-199 |
| 0299AJ | 20 | | GA | | 8-6 | 35-21-13 | D07348 | | | | SM00059 | | 9 | | 001-099 |
| 0299AJ | 20 | | GA | | 9-8 | 35-21-13 | D07348 | | | | SM00059 | | 9 | | 115-199 |
| 0300K | 18 | | GA | | 8-6 | 35-21-13 | D07348 | | | | SM00060 | | 9 | | 001-099 |
| 0300K | 18 | | GA | | 9-8 | 35-21-13 | D07348 | | | | SM00060 | | 9 | | 115-199 |
| 0391G | 16 | | GA | | 10-6 | 33-24-14 | D07010 | | | | SM00031 | | 9 | | 001-099 |
| 0391G | 16 | | GA | | 10-9 | 33-24-14 | D07010 | | | | SM00031 | | 9 | | 115-199 |
| 0392WV | 22 | | GA | | 10-6 | 33-25-14 | D07010 | | | | SM00032 | | 9 | | 001-099 |
| 0392WV | 22 | | GA | | 10-9 | 33-25-14 | D07010 | | | | SM00032 | | 9 | | 115-199 |
| 0393WG | 22 | | GA | | 10-6 | 33-25-14 | D07010 | | | | SM00033 | | 9 | | 001-099 |
| 0393WG | 22 | | GA | | 10-9 | 33-25-14 | D07010 | | | | SM00033 | | 9 | | 115-199 |
| 0395V | 22 | | GA | | 10-6 | 33-25-14 | D07010 | | | | SM00035 | | 9 | | 001-099 |
| 0395V | 22 | | GA | | 10-9 | 33-25-14 | D07010 | | | | SM00035 | | 9 | | 115-199 |
| 0396WN | 16 | | GA | | 10-6 | 33-23-13 | D07010 | | | | SM00036 | | 9 | | 001-099 |
| 0396WN | 16 | | GA | | 10-9 | 33-23-13 | D07010 | | | | SM00036 | | 9 | | 115-199 |
| 0397W | 20 | | GA | | 10-6 | 33-24-14 | D07010 | | | | SM00037 | | 9 | | 001-099 |
| 0397W | 20 | | GA | | 10-9 | 33-24-14 | D07010 | | | | SM00037 | | 9 | | 115-199 |
| 0398WP | 16 | | GA | | 10-6 | 33-23-13 | D07010 | | | | SM00038 | | 9 | | 001-099 |
| 0398WP | 16 | | GA | | 10-9 | 33-23-13 | D07010 | | | | SM00038 | | 9 | | 115-199 |
| 0399AJ | 20 | | GA | | 10-6 | 35-21-13 | D07010 | | | | SM00039 | | 9 | | 001-099 |
| 0399AJ | 20 | | GA | | 10-9 | 35-21-13 | D07010 | | | | SM00039 | | 9 | | 115-199 |
| 0400K | 18 | | GA | | 10-6 | 35-21-13 | D07010 | | | | SM00040 | | 9 | | 001-099 |
| 0400K | 18 | | GA | | 10-9 | 35-21-13 | D07010 | | | | SM00040 | | 9 | | 115-199 |
| 0411G | 16 | | GA | | 6-7 | 33-24-14 | SM00011 | | | 9 | SM00031 | | 9 | | 001-099 |
| 0411G | 16 | | GA | | 7-6 | 33-24-14 | SM00011 | | | 9 | SM00031 | | 9 | | 115-199 |
| 0412WV | 22 | | GA | | 6-7 | 33-25-14 | SM00012 | | | 9 | SM00032 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 45

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | |
| 0412WV | 22 | | GA | | 7-6 | 33-25-14 | | SM00012 | | | | 9 | | | | 115-199 |
| 0413WG | 22 | | GA | | 6-7 | 33-25-14 | | SM00013 | | | | 9 | | | | 001-099 |
| 0413WG | 22 | | GA | | 7-6 | 33-25-14 | | SM00013 | | | | 9 | | | | 115-199 |
| 0415V | 22 | | GA | | 6-7 | 33-25-14 | | SM00015 | | | | 9 | | | | 001-099 |
| 0415V | 22 | | GA | | 7-6 | 33-25-14 | | SM00015 | | | | 9 | | | | 115-199 |
| 0416WN | 16 | | GA | | 6-7 | 33-23-13 | | SM00016 | | | | 9 | | | | 001-099 |
| 0416WN | 16 | | GA | | 7-6 | 33-23-13 | | SM00016 | | | | 9 | | | | 115-199 |
| 0417W | 20 | | GA | | 6-7 | 33-24-14 | | SM00017 | | | | 9 | | | | 001-099 |
| 0417W | 20 | | GA | | 7-6 | 33-24-14 | | SM00017 | | | | 9 | | | | 115-199 |
| 0418WP | 16 | | GA | | 6-7 | 33-23-13 | | SM00018 | | | | 9 | | | | 001-099 |
| 0418WP | 16 | | GA | | 7-6 | 33-23-13 | | SM00018 | | | | 9 | | | | 115-199 |
| 0419AJ | 16 | | GA | | 6-7 | 35-21-13 | | SM00019 | | | | 9 | | | | 001-099 |
| 0419AJ | 16 | | GA | | 7-6 | 35-21-13 | | SM00019 | | | | 9 | | | | 115-199 |
| 0420K | 18 | | GA | | 6-7 | 35-21-13 | | SM00020 | | | | 9 | | | | 001-099 |
| 0420K | 18 | | GA | | 7-6 | 35-21-13 | | SM00020 | | | | 9 | | | | 115-199 |
| 0431G | 16 | | GA | | 7-6 | 33-24-14 | | SM00031 | | | | 9 | | | | 001-099 |
| 0431G | 16 | | GA | | 8-6 | 33-24-14 | | SM00031 | | | | 9 | | | | 115-199 |
| 0432WV | 22 | | GA | | 7-6 | 33-25-14 | | SM00032 | | | | 9 | | | | 001-099 |
| 0432WV | 22 | | GA | | 8-6 | 33-25-14 | | SM00032 | | | | 9 | | | | 115-199 |
| 0435V | 22 | | GA | | 7-6 | 33-25-14 | | SM00035 | | | | 9 | | | | 001-099 |
| 0435V | 22 | | GA | | 8-6 | 33-25-14 | | SM00035 | | | | 9 | | | | 115-199 |
| 0437W | 20 | | GA | | 7-6 | 33-24-14 | | SM00037 | | | | 9 | | | | 001-099 |
| 0437W | 20 | | GA | | 8-6 | 33-24-14 | | SM00037 | | | | 9 | | | | 115-199 |
| 0438WP | 16 | | GA | | 7-6 | 33-23-13 | | SM00038 | | | | 9 | | | | 001-099 |
| 0438WP | 16 | | GA | | 8-6 | 33-23-13 | | SM00038 | | | | 9 | | | | 115-199 |
| 0439AJ | 16 | | GA | | 7-6 | 35-21-13 | | SM00039 | | | | 9 | | | | 001-099 |
| 0439AJ | 16 | | GA | | 8-6 | 35-21-13 | | SM00039 | | | | 9 | | | | 115-199 |
| 0440K | 18 | | GA | | 7-6 | 35-21-13 | | SM00040 | | | | 9 | | | | 001-099 |
| 0440K | 18 | | GA | | 8-6 | 35-21-13 | | SM00040 | | | | 9 | | | | 115-199 |
| 0451G | 16 | | GA | | 7-5 | 33-24-14 | | SM00051 | | | | 9 | | | | 001-099 |
| 0451G | 16 | | GA | | 7-9 | 33-24-14 | | SM00051 | | | | 9 | | | | 115-199 |
| 0452WV | 22 | | GA | | 7-5 | 33-25-14 | | SM00052 | | | | 9 | | | | 001-099 |
| 0452WV | 22 | | GA | | 7-9 | 33-25-14 | | SM00052 | | | | 9 | | | | 115-199 |
| 0453WG | 22 | | GA | | 7-5 | 33-25-14 | | SM00053 | | | | 9 | | | | 001-099 |
| 0453WG | 22 | | GA | | 7-9 | 33-25-14 | | SM00053 | | | | 9 | | | | 115-199 |
| 0455V | 22 | | GA | | 7-5 | 33-25-14 | | SM00055 | | | | 9 | | | | 001-099 |
| 0455V | 22 | | GA | | 7-9 | 33-25-14 | | SM00055 | | | | 9 | | | | 115-199 |
| 0456WN | 16 | | GA | | 7-5 | 33-23-14 | | SM00056 | | | | 9 | | | | 001-099 |
| 0456WN | 16 | | GA | | 7-9 | 33-23-14 | | SM00056 | | | | 9 | | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 46

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | |
| 0457W | 20 | GA | | | 7-5 | 33-24-14 | SM00057 | | | 9 | SM00077 | | | 9 | 001-099 |
| 0457W | 20 | GA | | | 7-9 | 33-24-14 | SM00057 | | | 9 | SM00077 | | | 9 | 115-199 |
| 0458WP | 16 | GA | | | 7-5 | 33-23-14 | SM00058 | | | 9 | SM00078 | | | 9 | 001-099 |
| 0458WP | 16 | GA | | | 7-9 | 33-23-14 | SM00058 | | | 9 | SM00078 | | | 9 | 115-199 |
| 0459AJ | 16 | GA | | | 7-5 | 35-21-13 | SM00059 | | | 9 | SM00079 | | | 9 | 001-099 |
| 0459AJ | 16 | GA | | | 7-9 | 35-21-13 | SM00059 | | | 9 | SM00079 | | | 9 | 115-199 |
| 0460K | 18 | GA | | | 7-5 | 35-21-13 | SM00060 | | | 9 | SM00080 | | | 9 | 001-099 |
| 0460K | 18 | GA | | | 7-9 | 35-21-13 | SM00060 | | | 9 | SM00080 | | | 9 | 115-199 |
| 0471G | 16 | GA | | | 5-4 | 33-24-14 | SM00071 | | | 9 | SM00091 | | | 9 | 001-099 |
| 0471G | 16 | GA | | | 6-5 | 33-24-14 | SM00071 | | | 9 | SM00091 | | | 9 | 115-199 |
| 0472WV | 22 | GA | | | 5-4 | 33-25-14 | SM00072 | | | 9 | SM00092 | | | 9 | 001-099 |
| 0472WV | 22 | GA | | | 6-5 | 33-25-14 | SM00072 | | | 9 | SM00092 | | | 9 | 115-199 |
| 0473WG | 22 | GA | | | 5-4 | 33-25-14 | SM00073 | | | 9 | SM00093 | | | 9 | 001-099 |
| 0473WG | 22 | GA | | | 6-5 | 33-25-14 | SM00073 | | | 9 | SM00093 | | | 9 | 115-199 |
| 0475V | 22 | GA | | | 5-4 | 33-25-14 | SM00075 | | | 9 | SM00095 | | | 9 | 001-099 |
| 0475V | 22 | GA | | | 6-5 | 33-25-14 | SM00075 | | | 9 | SM00095 | | | 9 | 115-199 |
| 0476WN | 16 | GA | | | 5-4 | 33-23-14 | SM00076 | | | 9 | SM00096 | | | 9 | 001-099 |
| 0476WN | 16 | GA | | | 6-5 | 33-23-14 | SM00076 | | | 9 | SM00096 | | | 9 | 115-199 |
| 0477W | 20 | GA | | | 5-4 | 33-24-14 | SM00077 | | | 9 | SM00097 | | | 9 | 001-099 |
| 0477W | 20 | GA | | | 6-5 | 33-24-14 | SM00077 | | | 9 | SM00097 | | | 9 | 115-199 |
| 0478WP | 16 | GA | | | 5-4 | 33-23-14 | SM00078 | | | 9 | SM00098 | | | 9 | 001-099 |
| 0478WP | 16 | GA | | | 6-5 | 33-23-14 | SM00078 | | | 9 | SM00098 | | | 9 | 115-199 |
| 0479AJ | 16 | GA | | | 5-4 | 35-21-13 | SM00079 | | | 9 | SM00099 | | | 9 | 001-099 |
| 0479AJ | 16 | GA | | | 6-5 | 35-21-13 | SM00079 | | | 9 | SM00099 | | | 9 | 115-199 |
| 0480K | 18 | GA | | | 5-4 | 35-21-13 | SM00080 | | | 9 | SM00100 | | | 9 | 001-099 |
| 0480K | 18 | GA | | | 6-5 | 35-21-13 | SM00080 | | | 9 | SM00100 | | | 9 | 115-199 |
| 0491G | 16 | GA | | | 7-2 | 33-24-14 | SM00091 | | | 9 | SM00111 | | | 9 | 001-099 |
| 0491G | 16 | GA | | | 7-10 | 33-24-14 | SM00091 | | | 9 | SM00111 | | | 9 | 115-199 |
| 0492WV | 22 | GA | | | 7-2 | 33-25-14 | SM00092 | | | 9 | SM00112 | | | 9 | 001-099 |
| 0492WV | 22 | GA | | | 7-10 | 33-25-14 | SM00092 | | | 9 | SM00112 | | | 9 | 115-199 |
| 0493WG | 22 | GA | | | 7-2 | 33-25-14 | SM00093 | | | 9 | SM00113 | | | 9 | 001-099 |
| 0493WG | 22 | GA | | | 7-10 | 33-25-14 | SM00093 | | | 9 | SM00113 | | | 9 | 115-199 |
| 0495V | 22 | GA | | | 7-2 | 33-25-14 | SM00095 | | | 9 | SM00115 | | | 9 | 001-099 |
| 0495V | 22 | GA | | | 7-10 | 33-25-14 | SM00095 | | | 9 | SM00115 | | | 9 | 115-199 |
| 0496WN | 16 | GA | | | 7-2 | 33-23-14 | SM00096 | | | 9 | SM00116 | | | 9 | 001-099 |
| 0496WN | 16 | GA | | | 7-10 | 33-23-14 | SM00096 | | | 9 | SM00116 | | | 9 | 115-199 |
| 0497W | 20 | GA | | | 7-2 | 33-24-14 | SM00097 | | | 9 | SM00117 | | | 9 | 001-099 |
| 0497W | 20 | GA | | | 7-10 | 33-24-14 | SM00097 | | | 9 | SM00117 | | | 9 | 115-199 |
| 0498WP | 16 | GA | | | 7-2 | 33-23-14 | SM00098 | | | 9 | SM00118 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 47

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|-----------------------------------|----------|---------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3706 | 286N3706 | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | | |
| 0498WP | 16 | GA | | 7-10 | 33-23-14 | | SM00098 | | | 9 | | SM00118 | | 9 | | 115-199 |
| 0499AJ | 16 | GA | | 7-2 | 35-21-13 | | SM00099 | | | 9 | | SM00119 | | 9 | | 001-099 |
| 0499AJ | 16 | GA | | 7-10 | 35-21-13 | | SM00099 | | | 9 | | SM00119 | | 9 | | 115-199 |
| 0500K | 18 | GA | | 7-2 | 35-21-13 | | SM00100 | | | 9 | | SM00120 | | 9 | | 001-099 |
| 0500K | 18 | GA | | 7-10 | 35-21-13 | | SM00100 | | | 9 | | SM00120 | | 9 | | 115-199 |
| 0511G | 16 | GA | | 7-5 | 33-24-14 | | SM00111 | | | 9 | | SM00131 | | 9 | | 001-099 |
| 0511G | 16 | GA | | 7-11 | 33-24-14 | | SM00111 | | | 9 | | SM00131 | | 9 | | 115-199 |
| 0512WV | 22 | GA | | 7-5 | 33-25-14 | | SM00112 | | | 9 | | SM00132 | | 9 | | 001-099 |
| 0512WV | 22 | GA | | 7-11 | 33-25-14 | | SM00112 | | | 9 | | SM00132 | | 9 | | 115-199 |
| 0513WG | 22 | GA | | 7-5 | 33-25-14 | | SM00113 | | | 9 | | SM00133 | | 9 | | 001-099 |
| 0513WG | 22 | GA | | 7-11 | 33-25-14 | | SM00113 | | | 9 | | SM00133 | | 9 | | 115-199 |
| 0515V | 22 | GA | | 7-5 | 33-25-14 | | SM00115 | | | 9 | | SM00135 | | 9 | | 001-099 |
| 0515V | 22 | GA | | 7-11 | 33-25-14 | | SM00115 | | | 9 | | SM00135 | | 9 | | 115-199 |
| 0516WN | 16 | GA | | 7-5 | 33-23-14 | | SM00116 | | | 9 | | SM00136 | | 9 | | 001-099 |
| 0516WN | 16 | GA | | 7-11 | 33-23-14 | | SM00116 | | | 9 | | SM00136 | | 9 | | 115-199 |
| 0517W | 20 | GA | | 7-5 | 33-24-14 | | SM00117 | | | 9 | | SM00137 | | 9 | | 001-099 |
| 0517W | 20 | GA | | 7-11 | 33-24-14 | | SM00117 | | | 9 | | SM00137 | | 9 | | 115-199 |
| 0518WP | 16 | GA | | 7-5 | 33-23-14 | | SM00118 | | | 9 | | SM00138 | | 9 | | 001-099 |
| 0518WP | 16 | GA | | 7-11 | 33-23-14 | | SM00118 | | | 9 | | SM00138 | | 9 | | 115-199 |
| 0519AJ | 16 | GA | | 7-5 | 35-21-13 | | SM00119 | | | 9 | | SM00139 | | 9 | | 001-099 |
| 0519AJ | 16 | GA | | 7-11 | 35-21-13 | | SM00119 | | | 9 | | SM00139 | | 9 | | 115-199 |
| 0520K | 18 | GA | | 7-5 | 35-21-13 | | SM00120 | | | 9 | | SM00140 | | 9 | | 001-099 |
| 0520K | 18 | GA | | 7-11 | 35-21-13 | | SM00120 | | | 9 | | SM00140 | | 9 | | 115-199 |
| 0531G | 16 | GA | | 8-6 | 33-24-14 | | SM00131 | | | 9 | | SM00151 | | 9 | | 001-099 |
| 0531G | 16 | GA | | 9-0 | 33-24-14 | | SM00131 | | | 9 | | SM00151 | | 9 | | 115-199 |
| 0532WV | 22 | GA | | 8-6 | 33-25-14 | | SM00132 | | | 9 | | SM00152 | | 9 | | 001-099 |
| 0532WV | 22 | GA | | 9-0 | 33-25-14 | | SM00132 | | | 9 | | SM00152 | | 9 | | 115-199 |
| 0533WG | 22 | GA | | 8-6 | 33-25-14 | | SM00133 | | | 9 | | SM00153 | | 9 | | 001-099 |
| 0533WG | 22 | GA | | 9-0 | 33-25-14 | | SM00133 | | | 9 | | SM00153 | | 9 | | 115-199 |
| 0535V | 22 | GA | | 8-6 | 33-25-14 | | SM00135 | | | 9 | | SM00155 | | 9 | | 001-099 |
| 0535V | 22 | GA | | 9-0 | 33-25-14 | | SM00135 | | | 9 | | SM00155 | | 9 | | 115-199 |
| 0536WN | 16 | GA | | 8-6 | 33-23-14 | | SM00136 | | | 9 | | SM00156 | | 9 | | 001-099 |
| 0536WN | 16 | GA | | 9-0 | 33-23-14 | | SM00136 | | | 9 | | SM00156 | | 9 | | 115-199 |
| 0537W | 20 | GA | | 8-6 | 33-24-14 | | SM00137 | | | 9 | | SM00157 | | 9 | | 001-099 |
| 0537W | 20 | GA | | 9-0 | 33-24-14 | | SM00137 | | | 9 | | SM00157 | | 9 | | 115-199 |
| 0538WP | 16 | GA | | 8-6 | 33-23-14 | | SM00138 | | | 9 | | SM00158 | | 9 | | 001-099 |
| 0538WP | 16 | GA | | 9-0 | 33-23-14 | | SM00138 | | | 9 | | SM00158 | | 9 | | 115-199 |
| 0539AJ | 16 | GA | | 8-6 | 35-21-13 | | SM00139 | | | 9 | | SM00159 | | 9 | | 001-099 |
| 0539AJ | 16 | GA | | 9-0 | 35-21-13 | | SM00139 | | | 9 | | SM00159 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 48

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | |
| 0540K | 18 | | GA | | 8-6 | 35-21-13 | | SM00140 | | 9 | | SM00160 | | 9 | | 001-099 |
| 0540K | 18 | | GA | | 9-0 | 35-21-13 | | SM00140 | | 9 | | SM00160 | | 9 | | 115-199 |
| 0800 | 22 | | GA | | 9-3 | 23-31-41 | | D40314P | 12 | | | SM00001 | | 9 | | 001-099 |
| 0800 | 22 | | GA | | 8-7 | 23-31-41 | | D40314P | 12 | | | SM00001 | | 9 | | 115-199 |
| 0801 | 16 | | GA | | 4-3 | 33-24-14 | | D40314P | 1 | | | SM00011 | | 9 | | 001-099 |
| 0801 | 16 | | GA | | 3-7 | 33-24-14 | | D40314P | 1 | | | SM00011 | | 9 | | 115-199 |
| 0802 | 22 | | GA | | 4-3 | 33-25-14 | | D40314P | 2 | | | SM00012 | | 9 | | 001-099 |
| 0802 | 22 | | GA | | 3-7 | 33-25-14 | | D40314P | 2 | | | SM00012 | | 9 | | 115-199 |
| 0803 | 22 | | GA | | 4-3 | 33-25-14 | | D40314P | 3 | | | SM00013 | | 9 | | 001-099 |
| 0803 | 22 | | GA | | 3-7 | 33-25-14 | | D40314P | 3 | | | SM00013 | | 9 | | 115-199 |
| 0804 | 22 | | GA | | 13-6 | 23-31-41 | | D07348 | 12 | | | SM00001 | | 9 | | 001-099 |
| 0804 | 22 | | GA | | 14-0 | 23-31-41 | | SM00001 | | 9 | | D07348 | 15 | | | 115-199 |
| 0805 | 22 | | GA | | 4-3 | 33-25-14 | | D40314P | 5 | | | SM00015 | | 9 | | 001-099 |
| 0805 | 22 | | GA | | 3-7 | 33-25-14 | | D40314P | 5 | | | SM00015 | | 9 | | 115-199 |
| 0806 | 16 | | GA | | 4-3 | 33-23-13 | | D40314P | 6 | | | SM00016 | | 9 | | 001-099 |
| 0806 | 16 | | GA | | 3-7 | 33-23-13 | | D40314P | 6 | | | SM00016 | | 9 | | 115-199 |
| 0807 | 20 | | GA | | 4-3 | 33-24-14 | | D40314P | 7 | | | SM00017 | | 9 | | 001-099 |
| 0807 | 20 | | GA | | 3-7 | 33-24-14 | | D40314P | 7 | | | SM00017 | | 9 | | 115-199 |
| 0808 | 16 | | GA | | 4-3 | 33-23-13 | | D40314P | 8 | | | SM00018 | | 9 | | 001-099 |
| 0808 | 16 | | GA | | 3-7 | 33-23-13 | | D40314P | 8 | | | SM00018 | | 9 | | 115-199 |
| 0809 | 16 | | GA | | 4-3 | 35-21-13 | | D40314P | 9 | | | SM00019 | | 9 | | 001-099 |
| 0809 | 16 | | GA | | 3-7 | 35-21-13 | | D40314P | 9 | | | SM00019 | | 9 | | 115-199 |
| 0810 | 18 | | GA | | 4-3 | 35-21-13 | | D40314P | 10 | | | SM00020 | | 9 | | 001-099 |
| 0810 | 18 | | GA | | 3-7 | 35-21-13 | | D40314P | 10 | | | SM00020 | | 9 | | 115-199 |
| 0811 | 22 | | GA | | 13-6 | 23-31-41 | | D05978 | 12 | | | SM00001 | | 9 | | 001-099 |
| 0811 | 22 | | GA | | 14-7 | 23-31-41 | | SM00001 | | 9 | | D05978 | 15 | | | 115-199 |
| 0816 | 22 | | GA | | 39-7 | 23-31-41 | | D40314P | 16 | | | D01243 | 3 | | | 001-099 |
| 0816 | 22 | | GA | | 35-8 | 23-31-41 | | D40314P | 16 | | | D01243 | 3 | | | 115-199 |
| 0824 | 20 | | GA | | 26-2 | 33-23-14 | | D40314P | 4 | | | T10014 | HV3 | E | | 001-099 |
| 0824 | 20 | | GA | | 25-0 | 33-23-14 | | D40314P | 4 | | | T10014 | HV3 | E | | 115-199 |
| 0825 | 14 | | GA | | 11-10 | 33-23-14 | | GD03263 | AC.. | E | | T10014 | GND | E | | ALL |
| 0826 | 16 | | GA | | 9-5 | 33-23-14 | | SM00076 | | 9 | | T10014 | LV | E | | 001-099 |
| 0826 | 16 | | GA | | 9-8 | 33-23-14 | | SM00076 | | 9 | | T10014 | LV | E | | 115-199 |
| 0851 | 16 | | GA | | 5-4 | 33-24-14 | | L00412 | 3 | C | | SM00111 | | 9 | | 001-099 |
| 0851 | 16 | | GA | | 6-5 | 33-24-14 | | L00412 | 3 | C | | SM00111 | | 9 | | 115-199 |
| 0857 | 20 | | GA | | 5-4 | 33-24-14 | | L00412 | 1 | C | | SM00117 | | 9 | | 001-099 |
| 0857 | 20 | | GA | | 6-5 | 33-24-14 | | L00412 | 1 | C | | SM00117 | | 9 | | 115-199 |
| 0858 | 20 | | GA | | 4-2 | 33-24-14 | | L00412 | 2 | C | | GD01631 | AC.. | E | | 001-099 |
| 0858 | 20 | | GA | | 3-8 | 33-24-14 | | L00412 | 2 | C | | GD01631 | AC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 49

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|-----------------------------------|----------|---------|-------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3706 | 286N3706 | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | | |
| 0877 | 20 | GA | | 14-6 | 35-21-13 | D04670 | | 1 | VY | | | SM00159 | | 9 | | 001-099 |
| 0877 | 20 | GA | | 14-10 | 35-21-13 | D04670 | | 1 | VY | | | SM00159 | | 9 | | 115-199 |
| 0878 | 18 | GA | | 2-0 | 35-21-13 | D04672 | | 1 | VG | | | GD02401 | DC.. | E | | ALL |
| 0880 | 16 | GA | | 9-9 | 33-24-14 | SM00151 | | | 9 | | | SP02030 | | 9 | | 001-099 |
| 0880 | 16 | GA | | 10-0 | 33-24-14 | SM00151 | | | 9 | | | SP02030 | | 9 | | 115-199 |
| 0881 | 20 | GA | | 9-9 | 33-24-14 | SM00157 | | | 9 | | | SP02028 | | 9 | | 001-099 |
| 0881 | 20 | GA | | 10-0 | 33-24-14 | SM00157 | | | 9 | | | SP02028 | | 9 | | 115-199 |
| 0920 | 18 | GA | | 3-0 | 35-21-13 | SM00020 | | | 9 | | | GD03247 | DC.. | E | | 001-099 |
| 0920 | 18 | GA | | 3-6 | 35-21-13 | SM00020 | | | 9 | | | GD03247 | DC.. | E | | 115-199 |
| 0921 | 16 | GA | | 6-4 | 33-23-14 | SM00058 | | | 9 | | | GD03261 | AC.. | E | | 001-099 |
| 0921 | 16 | GA | | 6-6 | 33-23-14 | SM00058 | | | 9 | | | GD03261 | AC.. | E | | 115-199 |
| 0922 | 16 | GA | | 4-10 | 33-23-14 | SM00138 | | | 9 | | | GD03257 | AC.. | E | | 001-099 |
| 0922 | 16 | GA | | 4-8 | 33-23-14 | SM00138 | | | 9 | | | GD03257 | AC.. | E | | 115-199 |
| 0923 | 16 | GA | | 5-5 | 33-23-14 | SM00158 | | | 9 | | | GD02507 | AC.. | E | | 001-099 |
| 0923 | 16 | GA | | 6-9 | 33-23-14 | SM00158 | | | 9 | | | GD02507 | AC.. | E | | 115-199 |
| 0938 | 16 | GA | | 2-11 | 33-23-14 | SM00098 | | | 9 | | | GD03265 | AC.. | E | | 001-099 |
| 0938 | 16 | GA | | 3-11 | 33-23-14 | SM00098 | | | 9 | | | GD03265 | AC.. | E | | 115-199 |
| 0939 | 18 | GA | | 6-2 | 35-21-13 | SM00140 | | | 9 | | | GD03269 | DC.. | E | | 001-099 |
| 0939 | 18 | GA | | 6-8 | 35-21-13 | SM00140 | | | 9 | | | GD03269 | DC.. | E | | 115-199 |
| 0940 | 18 | GA | | 2-11 | 35-21-13 | SM00100 | | | 9 | | | GD03249 | DC.. | E | | 001-099 |
| 0940 | 18 | GA | | 3-11 | 35-21-13 | SM00100 | | | 9 | | | GD03249 | DC.. | E | | 115-199 |
| 0944 | 22 | GA | | 11-0 | 33-25-14 | SM00033 | | | 9 | | | SP00544 | | 9 | | 001-099 |
| 0944 | 22 | GA | | 11-10 | 33-25-14 | SM00033 | | | 9 | | | SP00544 | | 9 | | 115-199 |
| 0948 | 22 | GA | | 13-4 | 33-25-14 | SM00153 | | | 9 | | | SP00548 | | 9 | | 001-099 |
| 0948 | 22 | GA | | 13-7 | 33-25-14 | SM00153 | | | 9 | | | SP00548 | | 9 | | 115-199 |
| 0965 | 22 | GA | | 14-2 | 33-25-14 | D40314P | | 19 | | | | SM00053 | | 9 | | 115-199 |
| 0966 | 22 | GA | | 13-7 | 33-25-14 | SM00152 | | | 9 | | | SP01130 | | 9 | | 115-199 |
| 0974 | 20 | GA | | 10-10 | 23-31-22 | D01243 | | 4 | | | | SM00160 | | 9 | | 001-099 |
| 0974 | 20 | GA | | 8-4 | 23-31-22 | D01243 | | 4 | | | | SM00160 | | 9 | | 115-199 |
| 2011B | 22 | GB | A | 7-9 | 23-31-22 | D05968 | | 14 | | | | SM00024 | | 9 | | 001-099 |
| 2011B | 22 | GB | A | 8-2 | 23-31-22 | D05968 | | 13 | | | | SM00023 | | 9 | | 115-199 |
| 2011R | 22 | GB | A | 0-0 | 23-31-22 | D05968 | | 13 | | | | SM00023 | | 9 | | 001-099 |
| 2011R | 22 | GB | A | 0-0 | 23-31-22 | D05968 | | 14 | | | | SM00024 | | 9 | | 115-199 |
| 2021B | 22 | GB | B | 8-3 | 23-31-22 | D05970 | | 14 | | | | SM00024 | | 9 | | 001-099 |
| 2021B | 22 | GB | B | 8-9 | 23-31-22 | D05970 | | 13 | | | | SM00023 | | 9 | | 115-199 |
| 2021R | 22 | GB | B | 0-0 | 23-31-22 | D05970 | | 13 | | | | SM00023 | | 9 | | 001-099 |
| 2021R | 22 | GB | B | 0-0 | 23-31-22 | D05970 | | 14 | | | | SM00024 | | 9 | | 115-199 |
| 2023B | 22 | GB | T | 6-7 | 23-31-22 | SM00024 | | | 9 | | | SM00044 | | 9 | | 001-099 |
| 2023B | 22 | GB | T | 7-6 | 23-31-22 | SM00023 | | | 9 | | | SM00043 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 50

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | | To | | | | | |
|------------|-------------|----|-------|-----------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | 286N3706 | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | | |
| 2023R | 22 | GB | T | | 0-0 | 23-31-22 | SM00023 | | | 9 | | SM00043 | | 9 | | 001-099 |
| 2023R | 22 | GB | T | | 0-0 | 23-31-22 | SM00024 | | | 9 | | SM00044 | | 9 | | 115-199 |
| 2031B | 22 | GB | C | | 8-6 | 23-31-22 | D05972 | | 14 | | | SM00044 | | 9 | | 001-099 |
| 2031B | 22 | GB | C | | 9-0 | 23-31-22 | D05972 | | 13 | | | SM00043 | | 9 | | 115-199 |
| 2031R | 22 | GB | C | | 0-0 | 23-31-22 | D05972 | | 13 | | | SM00043 | | 9 | | 001-099 |
| 2031R | 22 | GB | C | | 0-0 | 23-31-22 | D05972 | | 14 | | | SM00044 | | 9 | | 115-199 |
| 2041B | 22 | GB | D | | 7-4 | 23-31-22 | D05974 | | 14 | | | SM00044 | | 9 | | 001-099 |
| 2041B | 22 | GB | D | | 7-9 | 23-31-22 | D05974 | | 13 | | | SM00043 | | 9 | | 115-199 |
| 2041R | 22 | GB | D | | 0-0 | 23-31-22 | D05974 | | 13 | | | SM00043 | | 9 | | 001-099 |
| 2041R | 22 | GB | D | | 0-0 | 23-31-22 | D05974 | | 14 | | | SM00044 | | 9 | | 115-199 |
| 2043B | 22 | GB | U | | 7-6 | 23-31-22 | SM00044 | | | 9 | | SM00064 | | 9 | | 001-099 |
| 2043B | 22 | GB | U | | 8-6 | 23-31-22 | SM00043 | | | 9 | | SM00063 | | 9 | | 115-199 |
| 2043R | 22 | GB | U | | 0-0 | 23-31-22 | SM00043 | | | 9 | | SM00063 | | 9 | | 001-099 |
| 2043R | 22 | GB | U | | 0-0 | 23-31-22 | SM00044 | | | 9 | | SM00064 | | 9 | | 115-199 |
| 2051B | 22 | GB | E | | 9-5 | 23-31-22 | D05976 | | 14 | | | SM00064 | | 9 | | 001-099 |
| 2051B | 22 | GB | E | | 9-5 | 23-31-22 | D05976 | | 13 | | | SM00063 | | 9 | | 115-199 |
| 2051R | 22 | GB | E | | 0-0 | 23-31-22 | D05976 | | 13 | | | SM00063 | | 9 | | 001-099 |
| 2051R | 22 | GB | E | | 0-0 | 23-31-22 | D05976 | | 14 | | | SM00064 | | 9 | | 115-199 |
| 2061B | 22 | GB | F | | 8-5 | 23-31-22 | D05978 | | 14 | | | SM00064 | | 9 | | 001-099 |
| 2061B | 22 | GB | F | | 9-0 | 23-31-22 | D05978 | | 13 | | | SM00063 | | 9 | | 115-199 |
| 2061R | 22 | GB | F | | 0-0 | 23-31-22 | D05978 | | 13 | | | SM00063 | | 9 | | 001-099 |
| 2061R | 22 | GB | F | | 0-0 | 23-31-22 | D05978 | | 14 | | | SM00064 | | 9 | | 115-199 |
| 2063B | 22 | GB | V | | 7-5 | 23-31-22 | SM00064 | | | 9 | | SM00084 | | 9 | | 001-099 |
| 2063B | 22 | GB | V | | 7-9 | 23-31-22 | SM00063 | | | 9 | | SM00083 | | 9 | | 115-199 |
| 2063R | 22 | GB | V | | 0-0 | 23-31-22 | SM00063 | | | 9 | | SM00083 | | 9 | | 001-099 |
| 2063R | 22 | GB | V | | 0-0 | 23-31-22 | SM00064 | | | 9 | | SM00084 | | 9 | | 115-199 |
| 2071B | 22 | GB | G | | 8-5 | 23-31-22 | D05980 | | 14 | | | SM00084 | | 9 | | 001-099 |
| 2071B | 22 | GB | G | | 8-8 | 23-31-22 | D05980 | | 13 | | | SM00083 | | 9 | | 115-199 |
| 2071R | 22 | GB | G | | 0-0 | 23-31-22 | D05980 | | 13 | | | SM00083 | | 9 | | 001-099 |
| 2071R | 22 | GB | G | | 0-0 | 23-31-22 | D05980 | | 14 | | | SM00084 | | 9 | | 115-199 |
| 2081B | 22 | GB | H | | 10-3 | 23-31-22 | D05982 | | 14 | | | SM00084 | | 9 | | 001-099 |
| 2081B | 22 | GB | H | | 10-6 | 23-31-22 | D05982 | | 13 | | | SM00083 | | 9 | | 115-199 |
| 2081R | 22 | GB | H | | 0-0 | 23-31-22 | D05982 | | 13 | | | SM00083 | | 9 | | 001-099 |
| 2081R | 22 | GB | H | | 0-0 | 23-31-22 | D05982 | | 14 | | | SM00084 | | 9 | | 115-199 |
| 2083B | 22 | GB | W | | 5-4 | 23-31-22 | SM00084 | | | 9 | | SM00104 | | 9 | | 001-099 |
| 2083B | 22 | GB | W | | 6-5 | 23-31-22 | SM00083 | | | 9 | | SM00103 | | 9 | | 115-199 |
| 2083R | 22 | GB | W | | 0-0 | 23-31-22 | SM00083 | | | 9 | | SM00103 | | 9 | | 001-099 |
| 2083R | 22 | GB | W | | 0-0 | 23-31-22 | SM00084 | | | 9 | | SM00104 | | 9 | | 115-199 |
| 2091B | 22 | GB | J | | 7-6 | 23-31-22 | D05984 | | 14 | | | SM00104 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 51

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | 286N3706 | | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | |
| 2091B | 22 | GB | J | | 7-10 | 23-31-22 | D05984 | 13 | | | SM00103 | 9 | | | 115-199 |
| 2091R | 22 | GB | J | | 0-0 | 23-31-22 | D05984 | 13 | | | SM00103 | 9 | | | 001-099 |
| 2091R | 22 | GB | J | | 0-0 | 23-31-22 | D05984 | 14 | | | SM00104 | 9 | | | 115-199 |
| 2101B | 22 | GB | K | | 8-8 | 23-31-22 | D05986 | 14 | | | SM00104 | 9 | | | 001-099 |
| 2101B | 22 | GB | K | | 9-0 | 23-31-22 | D05986 | 13 | | | SM00103 | 9 | | | 115-199 |
| 2101R | 22 | GB | K | | 0-0 | 23-31-22 | D05986 | 13 | | | SM00103 | 9 | | | 001-099 |
| 2101R | 22 | GB | K | | 0-0 | 23-31-22 | D05986 | 14 | | | SM00104 | 9 | | | 115-199 |
| 2103B | 22 | GB | X | | 7-2 | 23-31-22 | SM00104 | | 9 | | SM00124 | 9 | | | 001-099 |
| 2103B | 22 | GB | X | | 7-10 | 23-31-22 | SM00103 | | 9 | | SM00123 | 9 | | | 115-199 |
| 2103R | 22 | GB | X | | 0-0 | 23-31-22 | SM00103 | | 9 | | SM00123 | 9 | | | 001-099 |
| 2103R | 22 | GB | X | | 0-0 | 23-31-22 | SM00104 | | 9 | | SM00124 | 9 | | | 115-199 |
| 2111B | 22 | GB | L | | 9-4 | 23-31-22 | D05988 | 14 | | | SM00124 | 9 | | | 001-099 |
| 2111B | 22 | GB | L | | 10-1 | 23-31-22 | D05988 | 13 | | | SM00123 | 9 | | | 115-199 |
| 2111R | 22 | GB | L | | 0-0 | 23-31-22 | D05988 | 13 | | | SM00123 | 9 | | | 001-099 |
| 2111R | 22 | GB | L | | 0-0 | 23-31-22 | D05988 | 14 | | | SM00124 | 9 | | | 115-199 |
| 2121B | 22 | GB | M | | 8-7 | 23-31-22 | D05990 | 14 | | | SM00124 | 9 | | | 001-099 |
| 2121B | 22 | GB | M | | 8-10 | 23-31-22 | D05990 | 13 | | | SM00123 | 9 | | | 115-199 |
| 2121R | 22 | GB | M | | 0-0 | 23-31-22 | D05990 | 13 | | | SM00123 | 9 | | | 001-099 |
| 2121R | 22 | GB | M | | 0-0 | 23-31-22 | D05990 | 14 | | | SM00124 | 9 | | | 115-199 |
| 2123B | 22 | GB | Y | | 7-5 | 23-31-22 | SM00124 | | 9 | | SM00144 | 9 | | | 001-099 |
| 2123B | 22 | GB | Y | | 7-11 | 23-31-22 | SM00123 | | 9 | | SM00143 | 9 | | | 115-199 |
| 2123R | 22 | GB | Y | | 0-0 | 23-31-22 | SM00123 | | 9 | | SM00143 | 9 | | | 001-099 |
| 2123R | 22 | GB | Y | | 0-0 | 23-31-22 | SM00124 | | 9 | | SM00144 | 9 | | | 115-199 |
| 2131B | 22 | GB | N | | 9-5 | 23-31-22 | D05992 | 14 | | | SM00144 | 9 | | | 001-099 |
| 2131B | 22 | GB | N | | 8-10 | 23-31-22 | D05992 | 13 | | | SM00143 | 9 | | | 115-199 |
| 2131R | 22 | GB | N | | 0-0 | 23-31-22 | D05992 | 13 | | | SM00143 | 9 | | | 001-099 |
| 2131R | 22 | GB | N | | 0-0 | 23-31-22 | D05992 | 14 | | | SM00144 | 9 | | | 115-199 |
| 2141B | 22 | GB | P | | 8-3 | 23-31-22 | D05994 | 14 | | | SM00144 | 9 | | | 001-099 |
| 2141B | 22 | GB | P | | 8-6 | 23-31-22 | D05994 | 13 | | | SM00143 | 9 | | | 115-199 |
| 2141R | 22 | GB | P | | 0-0 | 23-31-22 | D05994 | 13 | | | SM00143 | 9 | | | 001-099 |
| 2141R | 22 | GB | P | | 0-0 | 23-31-22 | D05994 | 14 | | | SM00144 | 9 | | | 115-199 |
| 2143B | 22 | GB | Z | | 8-6 | 23-31-22 | SM00144 | | 9 | | SM00164 | 9 | | | 001-099 |
| 2143B | 22 | GB | Z | | 9-0 | 23-31-22 | SM00143 | | 9 | | SM00163 | 9 | | | 115-199 |
| 2143R | 22 | GB | Z | | 0-0 | 23-31-22 | SM00143 | | 9 | | SM00163 | 9 | | | 001-099 |
| 2143R | 22 | GB | Z | | 0-0 | 23-31-22 | SM00144 | | 9 | | SM00164 | 9 | | | 115-199 |
| 2151B | 22 | GB | Q | | 5-1 | 23-31-22 | D05996 | 14 | | | SM00164 | 9 | | | 001-099 |
| 2151B | 22 | GB | Q | | 5-4 | 23-31-22 | D05996 | 13 | | | SM00163 | 9 | | | 115-199 |
| 2151R | 22 | GB | Q | | 0-0 | 23-31-22 | D05996 | 13 | | | SM00163 | 9 | | | 001-099 |
| 2151R | 22 | GB | Q | | 0-0 | 23-31-22 | D05996 | 14 | | | SM00164 | 9 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 52

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3706 | 286N3706 | | | PSU HARNESS-LEFT, AFT (continued) | | | | | | | | | | | |
| 2161B | 22 | GB | R | | 4-11 | 23-31-22 | D05998 | | 14 | | SM00164 | | 9 | | 001-099 |
| 2161B | 22 | GB | R | | 5-3 | 23-31-22 | D05998 | | 13 | | SM00163 | | 9 | | 115-199 |
| 2161R | 22 | GB | R | | 0-0 | 23-31-22 | D05998 | | 13 | | SM00163 | | 9 | | 001-099 |
| 2161R | 22 | GB | R | | 0-0 | 23-31-22 | D05998 | | 14 | | SM00164 | | 9 | | 115-199 |
| 2181B | 22 | GB | AB | | 10-6 | 23-31-22 | D07010 | | 14 | | SM00044 | | 9 | | 001-099 |
| 2181B | 22 | GB | AB | | 10-9 | 23-31-22 | D07010 | | 13 | | SM00043 | | 9 | | 115-199 |
| 2181R | 22 | GB | AB | | 0-0 | 23-31-22 | D07010 | | 13 | | SM00043 | | 9 | | 001-099 |
| 2181R | 22 | GB | AB | | 0-0 | 23-31-22 | D07010 | | 14 | | SM00044 | | 9 | | 115-199 |
| 2191B | 22 | GB | AC | | 8-6 | 23-31-22 | D07348 | | 14 | | SM00064 | | 9 | | 001-099 |
| 2191B | 22 | GB | AC | | 9-8 | 23-31-22 | D07348 | | 13 | | SM00063 | | 9 | | 115-199 |
| 2191R | 22 | GB | AC | | 0-0 | 23-31-22 | D07348 | | 13 | | SM00063 | | 9 | | 001-099 |
| 2191R | 22 | GB | AC | | 0-0 | 23-31-22 | D07348 | | 14 | | SM00064 | | 9 | | 115-199 |
| 2413B | 22 | GB | S | | 4-3 | 23-31-22 | D40314P | | 14 | | SM00024 | | 9 | | 001-099 |
| 2413B | 22 | GB | S | | 3-7 | 23-31-22 | D40314P | | 13 | | SM00023 | | 9 | | 115-199 |
| 2413R | 22 | GB | S | | 0-0 | 23-31-22 | D40314P | | 13 | | SM00023 | | 9 | | 001-099 |
| 2413R | 22 | GB | S | | 0-0 | 23-31-22 | D40314P | | 14 | | SM00024 | | 9 | | 115-199 |
| 2471B | 22 | GB | AA | | 10-10 | 23-31-22 | D01243 | | 1 | | SM00164 | | 9 | | 001-099 |
| 2471B | 22 | GB | AA | | 8-4 | 23-31-22 | D01243 | | 1 | | SM00163 | | 9 | | 115-199 |
| 2471R | 22 | GB | AA | | 0-0 | 23-31-22 | D01243 | | 2 | | SM00163 | | 9 | | 001-099 |
| 2471R | 22 | GB | AA | | 0-0 | 23-31-22 | D01243 | | 2 | | SM00164 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3700

Page 53 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3724 | 286N3724 | | | FLUORESCENT LIGHTING-SIDEWALL,LEFT | | | | | | | | | | | |
| 0001 | 18 | | GA | | 16-0 | 33-21-32 | D03812 | | | 4 | SM00011 | | 9 | | ALL |
| 0002 | 20 | | GA | | 8-0 | 33-21-32 | D03812 | | | 5 | GD03547 | ST.. | E | | ALL |
| 0005 | 22 | | GA | | 16-0 | 33-21-32 | D03812 | | | 1 | SM00015 | | 9 | | ALL |
| 0006 | 20 | | GA | | 8-0 | 33-21-32 | D03812 | | | 6 | GD03521 | AC.. | E | | ALL |
| 0011 | 18 | | GA | | 16-0 | 33-21-32 | D03814 | | | 4 | SM00011 | | 9 | | ALL |
| 0012 | 20 | | GA | | 8-0 | 33-21-32 | D03814 | | | 5 | GD03547 | ST.. | E | | ALL |
| 0015 | 22 | | GA | | 16-0 | 33-21-32 | D03814 | | | 1 | SM00015 | | 9 | | ALL |
| 0016 | 20 | | GA | | 8-0 | 33-21-32 | D03814 | | | 6 | GD03521 | AC.. | E | | ALL |
| 0021 | 18 | | GA | | 10-0 | 33-21-32 | D03816 | | | 4 | SM00021 | | 9 | | ALL |
| 0022 | 20 | | GA | | 8-0 | 33-21-32 | D03816 | | | 5 | GD03553 | ST.. | E | | ALL |
| 0025 | 22 | | GA | | 10-0 | 33-21-32 | D03816 | | | 1 | SM00025 | | 9 | | ALL |
| 0026 | 20 | | GA | | 8-0 | 33-21-32 | D03816 | | | 6 | GD03523 | AC.. | E | | ALL |
| 0031 | 18 | | GA | | 10-0 | 33-21-32 | D03818 | | | 4 | SM00021 | | 9 | | ALL |
| 0032 | 20 | | GA | | 8-0 | 33-21-32 | D03818 | | | 5 | GD03553 | ST.. | E | | ALL |
| 0035 | 22 | | GA | | 10-0 | 33-21-32 | D03818 | | | 1 | SM00025 | | 9 | | ALL |
| 0036 | 20 | | GA | | 8-0 | 33-21-32 | D03818 | | | 6 | GD03523 | AC.. | E | | ALL |
| 0041 | 18 | | GA | | 24-0 | 33-21-32 | D06306 | | | 4 | SM00031 | | 9 | | ALL |
| 0042 | 20 | | GA | | 9-0 | 33-21-32 | D06306 | | | 5 | GD03555 | ST.. | E | | ALL |
| 0045 | 22 | | GA | | 24-0 | 33-21-32 | D06306 | | | 1 | SM00035 | | 9 | | ALL |
| 0046 | 20 | | GA | | 9-0 | 33-21-32 | D06306 | | | 6 | GD03526 | AC.. | E | | ALL |
| 0051 | 18 | | GA | | 24-0 | 33-21-32 | D06308 | | | 4 | SM00031 | | 9 | | ALL |
| 0052 | 20 | | GA | | 9-0 | 33-21-32 | D06308 | | | 5 | GD03555 | ST.. | E | | ALL |
| 0055 | 22 | | GA | | 24-0 | 33-21-32 | D06308 | | | 1 | SM00035 | | 9 | | ALL |
| 0056 | 20 | | GA | | 9-0 | 33-21-32 | D06308 | | | 6 | GD03526 | AC.. | E | | ALL |
| 0061 | 18 | | GA | | 15-0 | 33-21-32 | D07454 | | | 4 | SM00041 | | 9 | | ALL |
| 0062 | 20 | | GA | | 9-0 | 33-21-32 | D07454 | | | 5 | GD03658 | ST.. | E | | ALL |
| 0065 | 22 | | GA | | 15-0 | 33-21-32 | D07454 | | | 1 | SM00045 | | 9 | | ALL |
| 0066 | 20 | | GA | | 9-0 | 33-21-32 | D07454 | | | 6 | GD03660 | AC.. | E | | ALL |
| 0071 | 18 | | GA | | 15-0 | 33-21-32 | D07456 | | | 4 | SM00041 | | 9 | | ALL |
| 0072 | 20 | | GA | | 9-0 | 33-21-32 | D07456 | | | 5 | GD03658 | ST.. | E | | ALL |
| 0075 | 22 | | GA | | 15-0 | 33-21-32 | D07456 | | | 1 | SM00045 | | 9 | | ALL |
| 0076 | 20 | | GA | | 9-0 | 33-21-32 | D07456 | | | 6 | GD03660 | AC.. | E | | ALL |
| 0081 | 18 | | GA | | 18-0 | 33-21-32 | D07458 | | | 4 | SM00051 | | 9 | | ALL |
| 0082 | 20 | | GA | | 9-0 | 33-21-32 | D07458 | | | 5 | GD03561 | ST.. | E | | ALL |
| 0085 | 22 | | GA | | 18-0 | 33-21-32 | D07458 | | | 1 | SM00055 | | 9 | | ALL |
| 0086 | 20 | | GA | | 9-0 | 33-21-32 | D07458 | | | 6 | GD03529 | AC.. | E | | ALL |
| 0091 | 18 | | GA | | 18-0 | 33-21-32 | D07460 | | | 4 | SM00051 | | 9 | | ALL |
| 0092 | 20 | | GA | | 9-0 | 33-21-32 | D07460 | | | 5 | GD03561 | ST.. | E | | ALL |
| 0095 | 22 | | GA | | 18-0 | 33-21-32 | D07460 | | | 1 | SM00055 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3720

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3724 | 286N3724 | | | FLUORESCENT LIGHTING-SIDEWALL,LEFT (continued) | | | | | | | | | | | |
| 0096 | 20 | | GA | | 9-0 | 33-21-32 | D07460 | | 6 | | GD03529 | AC.. | E | | ALL |
| 0101 | 18 | | GA | | 13-0 | 33-21-32 | D07462 | | 4 | | SM00061 | | 9 | | ALL |
| 0102 | 20 | | GA | | 7-0 | 33-21-32 | D07462 | | 5 | | GD03565 | ST.. | E | | ALL |
| 0105 | 22 | | GA | | 13-0 | 33-21-32 | D07462 | | 1 | | SM00065 | | 9 | | ALL |
| 0106 | 20 | | GA | | 7-0 | 33-21-32 | D07462 | | 6 | | GD03530 | AC.. | E | | ALL |
| 0111 | 18 | | GA | | 13-0 | 33-21-32 | D07464 | | 4 | | SM00061 | | 9 | | ALL |
| 0112 | 20 | | GA | | 7-0 | 33-21-32 | D07464 | | 5 | | GD03565 | ST.. | E | | ALL |
| 0115 | 22 | | GA | | 13-0 | 33-21-32 | D07464 | | 1 | | SM00065 | | 9 | | ALL |
| 0116 | 20 | | GA | | 7-0 | 33-21-32 | D07464 | | 6 | | GD03530 | AC.. | E | | ALL |
| 0121 | 18 | | GA | | 10-0 | 33-21-32 | D07466 | | 4 | | SM00071 | | 9 | | ALL |
| 0122 | 20 | | GA | | 7-0 | 33-21-32 | D07466 | | 5 | | GD03567 | ST.. | E | | ALL |
| 0125 | 22 | | GA | | 10-0 | 33-21-32 | D07466 | | 1 | | SM00075 | | 9 | | ALL |
| 0126 | 20 | | GA | | 8-0 | 33-21-32 | D07466 | | 6 | | GD03531 | AC.. | E | | ALL |
| 0131 | 18 | | GA | | 10-0 | 33-21-32 | D07488 | | 4 | | SM00071 | | 9 | | ALL |
| 0132 | 20 | | GA | | 7-0 | 33-21-32 | D07488 | | 5 | | GD03567 | ST.. | E | | ALL |
| 0135 | 22 | | GA | | 10-0 | 33-21-32 | D07488 | | 1 | | SM00075 | | 9 | | ALL |
| 0136 | 20 | | GA | | 8-0 | 33-21-32 | D07488 | | 6 | | GD03531 | AC.. | E | | ALL |
| 0301 | 16 | | GA | | 44-0 | 33-21-32 | D40374P | | 1 | 16 | SM00011 | | 9 | | ALL |
| 0305 | 24 | | GK | | 44-0 | 33-21-32 | D40374P | | 3 | | SM00015 | | 9 | | ALL |
| 0311 | 18 | | GA | | 12-0 | 33-21-32 | SM00011 | | | 9 | SM00021 | | 9 | | ALL |
| 0315 | 24 | | GK | | 12-0 | 33-21-32 | SM00015 | | | 9 | SM00025 | | 9 | | ALL |
| 0321 | 18 | | GA | | 27-0 | 33-21-32 | SM00021 | | | 9 | SM00031 | | 9 | | ALL |
| 0325 | 24 | | GK | | 27-0 | 33-21-32 | SM00025 | | | 9 | SM00035 | | 9 | | ALL |
| 0331 | 18 | | GA | | 15-0 | 33-21-32 | SM00031 | | | 9 | SM00041 | | 9 | | ALL |
| 0335 | 24 | | GK | | 15-0 | 33-21-32 | SM00035 | | | 9 | SM00045 | | 9 | | ALL |
| 0341 | 18 | | GA | | 20-0 | 33-21-32 | SM00041 | | | 9 | SM00051 | | 9 | | ALL |
| 0345 | 24 | | GK | | 20-0 | 33-21-32 | SM00045 | | | 9 | SM00055 | | 9 | | ALL |
| 0351 | 18 | | GA | | 10-0 | 33-21-32 | SM00051 | | | 9 | SM00061 | | 9 | | ALL |
| 0355 | 24 | | GK | | 10-0 | 33-21-32 | SM00055 | | | 9 | SM00065 | | 9 | | ALL |
| 0361 | 18 | | GA | | 5-0 | 33-21-32 | SM00061 | | | 9 | SM00071 | | 9 | | ALL |
| 0365 | 24 | | GK | | 5-0 | 33-21-32 | SM00065 | | | 9 | SM00075 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3720

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD | | | | | | | | | | | |
| 0011G | 16 | | GA | | 12-0 | 33-24-21 | | D06000 | | | | SM00011 | | 9 | | ALL |
| 0012WV | 22 | | GA | | 12-0 | 33-25-21 | | D06000 | | | | SM00012 | | 9 | | ALL |
| 0013WG | 22 | | GA | | 12-0 | 33-25-21 | | D06000 | | | | SM00013 | | 9 | | ALL |
| 0014WO | 22 | | GA | | 12-0 | 33-25-21 | | D06000 | | | | SM00014 | | 9 | | ALL |
| 0015V | 22 | | GA | | 12-0 | 33-25-21 | | D06000 | | | | SM00015 | | 9 | | ALL |
| 0016WN | 16 | | GA | | 12-0 | 33-23-21 | | D06000 | | | | SM00016 | | 9 | | ALL |
| 0017W | 20 | | GA | | 12-0 | 33-24-21 | | D06000 | | | | SM00017 | | 9 | | ALL |
| 0018WP | 16 | | GA | | 12-0 | 33-23-21 | | D06000 | | | | SM00018 | | 9 | | ALL |
| 0019AJ | 20 | | GA | | 12-0 | 35-21-21 | | D06000 | 11 | | | SM00019 | | 9 | | ALL |
| 0020K | 18 | | GA | | 12-0 | 35-21-21 | | D06000 | 10 | | | SM00020 | | 9 | | ALL |
| 0021G | 16 | | GA | | 12-0 | 33-24-21 | | D06002 | 1 | | | SM00011 | | 9 | | ALL |
| 0022WV | 22 | | GA | | 12-0 | 33-25-21 | | D06002 | 2 | | | SM00012 | | 9 | | ALL |
| 0023WG | 22 | | GA | | 12-0 | 33-25-21 | | D06002 | 3 | | | SM00013 | | 9 | | ALL |
| 0024WO | 22 | | GA | | 12-0 | 33-25-21 | | D06002 | 4 | | | SM00014 | | 9 | | ALL |
| 0025V | 22 | | GA | | 12-0 | 33-25-21 | | D06002 | 5 | | | SM00015 | | 9 | | ALL |
| 0026WN | 16 | | GA | | 12-0 | 33-23-21 | | D06002 | 6 | | | SM00016 | | 9 | | ALL |
| 0027W | 20 | | GA | | 12-0 | 33-24-21 | | D06002 | 7 | | | SM00017 | | 9 | | ALL |
| 0028WP | 16 | | GA | | 12-0 | 33-23-21 | | D06002 | 8 | | | SM00018 | | 9 | | ALL |
| 0029AJ | 20 | | GA | | 12-0 | 35-21-21 | | D06002 | 11 | | | SM00019 | | 9 | | ALL |
| 0030K | 18 | | GA | | 12-0 | 35-21-21 | | D06002 | 10 | | | SM00020 | | 9 | | ALL |
| 0031G | 16 | | GA | | 8-0 | 33-24-21 | | D06004 | 1 | | | SM00031 | | 9 | | ALL |
| 0032WV | 22 | | GA | | 8-0 | 33-25-21 | | D06004 | 2 | | | SM00032 | | 9 | | ALL |
| 0033WG | 22 | | GA | | 8-0 | 33-25-21 | | D06004 | 3 | | | SM00033 | | 9 | | ALL |
| 0034WO | 22 | | GA | | 8-0 | 33-25-21 | | D06004 | 4 | | | SM00034 | | 9 | | ALL |
| 0035V | 22 | | GA | | 8-0 | 33-25-21 | | D06004 | 5 | | | SM00035 | | 9 | | ALL |
| 0036WN | 16 | | GA | | 8-0 | 33-23-21 | | D06004 | 6 | | | SM00036 | | 9 | | ALL |
| 0037W | 20 | | GA | | 8-0 | 33-24-21 | | D06004 | 7 | | | SM00037 | | 9 | | ALL |
| 0038WP | 16 | | GA | | 8-0 | 33-23-21 | | D06004 | 8 | | | SM00038 | | 9 | | ALL |
| 0039AJ | 20 | | GA | | 8-0 | 35-21-21 | | D06004 | 11 | | | SM00039 | | 9 | | ALL |
| 0040K | 18 | | GA | | 8-0 | 35-21-21 | | D06004 | 10 | | | SM00040 | | 9 | | ALL |
| 0041G | 16 | | GA | | 10-0 | 33-24-21 | | D06006 | 1 | | | SM00031 | | 9 | | ALL |
| 0042WV | 22 | | GA | | 10-0 | 33-25-21 | | D06006 | 2 | | | SM00032 | | 9 | | ALL |
| 0043WG | 22 | | GA | | 10-0 | 33-25-21 | | D06006 | 3 | | | SM00033 | | 9 | | ALL |
| 0044WO | 22 | | GA | | 10-0 | 33-25-21 | | D06006 | 4 | | | SM00034 | | 9 | | ALL |
| 0045V | 22 | | GA | | 10-0 | 33-25-21 | | D06006 | 5 | | | SM00035 | | 9 | | ALL |
| 0046WN | 16 | | GA | | 10-0 | 33-23-21 | | D06006 | 6 | | | SM00036 | | 9 | | ALL |
| 0047W | 20 | | GA | | 10-0 | 33-24-21 | | D06006 | 7 | | | SM00037 | | 9 | | ALL |
| 0048WP | 16 | | GA | | 10-0 | 33-23-21 | | D06006 | 8 | | | SM00038 | | 9 | | ALL |
| 0049AJ | 20 | | GA | | 10-0 | 35-21-21 | | D06006 | 11 | | | SM00039 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | |
| 0050K | 18 | GA | | | 10-0 | 35-21-21 | D06006 | 10 | | | SM00040 | 9 | | | ALL |
| 0051G | 16 | GA | | | 8-0 | 33-24-21 | D06008 | 1 | | | SM00051 | 9 | | | ALL |
| 0052WV | 22 | GA | | | 8-0 | 33-25-21 | D06008 | 2 | | | SM00052 | 9 | | | ALL |
| 0053WG | 22 | GA | | | 8-0 | 33-25-21 | D06008 | 3 | | | SM00053 | 9 | | | ALL |
| 0054WO | 22 | GA | | | 8-0 | 33-25-21 | D06008 | 4 | | | SM00054 | 9 | | | ALL |
| 0055V | 22 | GA | | | 8-0 | 33-25-21 | D06008 | 5 | | | SM00055 | 9 | | | ALL |
| 0056WN | 16 | GA | | | 8-0 | 33-23-21 | D06008 | 6 | | | SM00056 | 9 | | | ALL |
| 0057W | 20 | GA | | | 8-0 | 33-24-21 | D06008 | 7 | | | SM00057 | 9 | | | ALL |
| 0058WP | 16 | GA | | | 8-0 | 33-23-21 | D06008 | 8 | | | SM00058 | 9 | | | ALL |
| 0059AJ | 20 | GA | | | 8-0 | 35-21-21 | D06008 | 11 | | | SM00059 | 9 | | | ALL |
| 0060K | 18 | GA | | | 8-0 | 35-21-21 | D06008 | 10 | | | SM00060 | 9 | | | ALL |
| 0061G | 16 | GA | | | 11-0 | 33-24-21 | D06010 | 1 | | | SM00051 | 9 | | | ALL |
| 0062WV | 22 | GA | | | 11-0 | 33-25-21 | D06010 | 2 | | | SM00052 | 9 | | | ALL |
| 0063WG | 22 | GA | | | 11-0 | 33-25-21 | D06010 | 3 | | | SM00053 | 9 | | | ALL |
| 0064WO | 22 | GA | | | 11-0 | 33-25-21 | D06010 | 4 | | | SM00054 | 9 | | | ALL |
| 0065V | 22 | GA | | | 11-0 | 33-25-21 | D06010 | 5 | | | SM00055 | 9 | | | ALL |
| 0066WN | 16 | GA | | | 11-0 | 33-23-21 | D06010 | 6 | | | SM00056 | 9 | | | ALL |
| 0067W | 20 | GA | | | 11-0 | 33-24-21 | D06010 | 7 | | | SM00057 | 9 | | | ALL |
| 0068WP | 16 | GA | | | 11-0 | 33-23-21 | D06010 | 8 | | | SM00058 | 9 | | | ALL |
| 0069AJ | 20 | GA | | | 11-0 | 35-21-21 | D06010 | 11 | | | SM00059 | 9 | | | ALL |
| 0070K | 18 | GA | | | 11-0 | 35-21-21 | D06010 | 10 | | | SM00060 | 9 | | | ALL |
| 0071G | 16 | GA | | | 9-0 | 33-24-21 | D06012 | 1 | | | SM00071 | 9 | | | ALL |
| 0072WV | 22 | GA | | | 8-0 | 33-25-21 | D06012 | 2 | | | SM00072 | 9 | | | ALL |
| 0073WG | 22 | GA | | | 8-0 | 33-25-21 | D06012 | 3 | | | SM00073 | 9 | | | ALL |
| 0074WO | 22 | GA | | | 8-0 | 33-25-21 | D06012 | 4 | | | SM00074 | 9 | | | ALL |
| 0075V | 22 | GA | | | 8-0 | 33-25-21 | D06012 | 5 | | | SM00075 | 9 | | | ALL |
| 0076WN | 16 | GA | | | 8-0 | 33-23-21 | D06012 | 6 | | | SM00076 | 9 | | | ALL |
| 0077W | 20 | GA | | | 8-0 | 33-24-21 | D06012 | 7 | | | SM00077 | 9 | | | ALL |
| 0078WP | 16 | GA | | | 8-0 | 33-23-21 | D06012 | 8 | | | SM00078 | 9 | | | ALL |
| 0079AJ | 20 | GA | | | 8-0 | 35-21-21 | D06012 | 11 | | | SM00079 | 9 | | | ALL |
| 0080K | 18 | GA | | | 8-0 | 35-21-21 | D06012 | 10 | | | SM00080 | 9 | | | ALL |
| 0081G | 16 | GA | | | 9-0 | 33-24-21 | D06014 | 1 | | | SM00071 | 9 | | | ALL |
| 0082WV | 22 | GA | | | 9-0 | 33-25-21 | D06014 | 2 | | | SM00072 | 9 | | | ALL |
| 0083WG | 22 | GA | | | 9-0 | 33-25-21 | D06014 | 3 | | | SM00073 | 9 | | | ALL |
| 0084WO | 22 | GA | | | 9-0 | 33-25-21 | D06014 | 4 | | | SM00074 | 9 | | | ALL |
| 0085V | 22 | GA | | | 9-0 | 33-25-21 | D06014 | 5 | | | SM00075 | 9 | | | ALL |
| 0086WN | 16 | GA | | | 9-0 | 33-23-21 | D06014 | 6 | | | SM00076 | 9 | | | ALL |
| 0087W | 20 | GA | | | 9-0 | 33-24-21 | D06014 | 7 | | | SM00077 | 9 | | | ALL |
| 0088WP | 16 | GA | | | 9-0 | 33-23-21 | D06014 | 8 | | | SM00078 | 9 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | |
| 0089AJ | 20 | | GA | | 9-0 | 35-21-21 | | D06014 | | 11 | | SM00079 | | 9 | | ALL |
| 0090K | 18 | | GA | | 9-0 | 35-21-21 | | D06014 | | 10 | | SM00080 | | 9 | | ALL |
| 0091G | 16 | | GA | | 9-0 | 33-24-21 | | D06016 | | 1 | | SM00091 | | 9 | | ALL |
| 0092WV | 22 | | GA | | 9-0 | 33-25-21 | | D06016 | | 2 | | SM00092 | | 9 | | ALL |
| 0093WG | 22 | | GA | | 9-0 | 33-25-21 | | D06016 | | 3 | | SM00093 | | 9 | | ALL |
| 0094WO | 22 | | GA | | 9-0 | 33-25-21 | | D06016 | | 4 | | SM00094 | | 9 | | ALL |
| 0095V | 22 | | GA | | 9-0 | 33-25-21 | | D06016 | | 5 | | SM00095 | | 9 | | ALL |
| 0096WN | 16 | | GA | | 9-0 | 33-23-21 | | D06016 | | 6 | | SM00096 | | 9 | | ALL |
| 0097W | 20 | | GA | | 9-0 | 33-24-21 | | D06016 | | 7 | | SM00097 | | 9 | | ALL |
| 0098WP | 16 | | GA | | 9-0 | 33-23-21 | | D06016 | | 8 | | SM00098 | | 9 | | ALL |
| 0099AJ | 20 | | GA | | 9-0 | 35-21-21 | | D06016 | | 11 | | SM00099 | | 9 | | ALL |
| 0100K | 18 | | GA | | 9-0 | 35-21-21 | | D06016 | | 10 | | SM00100 | | 9 | | ALL |
| 0101G | 16 | | GA | | 12-0 | 33-24-21 | | D06018 | | 1 | | SM00091 | | 9 | | ALL |
| 0102WV | 22 | | GA | | 12-0 | 33-25-21 | | D06018 | | 2 | | SM00092 | | 9 | | ALL |
| 0103WG | 22 | | GA | | 12-0 | 33-25-21 | | D06018 | | 3 | | SM00093 | | 9 | | ALL |
| 0104WO | 22 | | GA | | 12-0 | 33-25-21 | | D06018 | | 4 | | SM00094 | | 9 | | ALL |
| 0105V | 22 | | GA | | 12-0 | 33-25-21 | | D06018 | | 5 | | SM00095 | | 9 | | ALL |
| 0106WN | 16 | | GA | | 12-0 | 33-23-21 | | D06018 | | 6 | | SM00096 | | 9 | | ALL |
| 0107W | 20 | | GA | | 12-0 | 33-24-21 | | D06018 | | 7 | | SM00097 | | 9 | | ALL |
| 0108WP | 16 | | GA | | 12-0 | 33-23-21 | | D06018 | | 8 | | SM00098 | | 9 | | ALL |
| 0109AJ | 20 | | GA | | 12-0 | 35-21-21 | | D06018 | | 11 | | SM00099 | | 9 | | ALL |
| 0110K | 18 | | GA | | 12-0 | 35-21-21 | | D06018 | | 10 | | SM00100 | | 9 | | ALL |
| 0111G | 16 | | GA | | 9-0 | 33-24-21 | | D06020 | | 1 | | SM00111 | | 9 | | ALL |
| 0112WV | 22 | | GA | | 9-0 | 33-25-21 | | D06020 | | 2 | | SM00112 | | 9 | | ALL |
| 0113WG | 22 | | GA | | 9-0 | 33-25-21 | | D06020 | | 3 | | SM00113 | | 9 | | ALL |
| 0114WO | 22 | | GA | | 9-0 | 33-25-21 | | D06020 | | 4 | | SM00114 | | 9 | | ALL |
| 0115V | 22 | | GA | | 9-0 | 33-25-21 | | D06020 | | 5 | | SM00115 | | 9 | | ALL |
| 0116WN | 16 | | GA | | 9-0 | 33-23-21 | | D06020 | | 6 | | SM00116 | | 9 | | ALL |
| 0117W | 20 | | GA | | 9-0 | 33-24-21 | | D06020 | | 7 | | SM00117 | | 9 | | ALL |
| 0118WP | 16 | | GA | | 9-0 | 33-23-21 | | D06020 | | 8 | | SM00118 | | 9 | | ALL |
| 0119AJ | 20 | | GA | | 9-0 | 35-21-21 | | D06020 | | 11 | | SM00119 | | 9 | | ALL |
| 0120K | 18 | | GA | | 9-0 | 35-21-21 | | D06020 | | 10 | | SM00120 | | 9 | | ALL |
| 0121G | 16 | | GA | | 10-0 | 33-24-21 | | D06022 | | 1 | | SM00111 | | 9 | | ALL |
| 0122WV | 22 | | GA | | 10-0 | 33-25-21 | | D06022 | | 2 | | SM00112 | | 9 | | ALL |
| 0123WG | 22 | | GA | | 10-0 | 33-25-21 | | D06022 | | 3 | | SM00113 | | 9 | | ALL |
| 0124WO | 22 | | GA | | 10-0 | 33-25-21 | | D06022 | | 4 | | SM00114 | | 9 | | ALL |
| 0125V | 22 | | GA | | 10-0 | 33-25-21 | | D06022 | | 5 | | SM00115 | | 9 | | ALL |
| 0126WN | 16 | | GA | | 10-0 | 33-23-21 | | D06022 | | 6 | | SM00116 | | 9 | | ALL |
| 0127W | 20 | | GA | | 10-0 | 33-24-21 | | D06022 | | 7 | | SM00117 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | |
| 0128WP | 16 | GA | | | 10-0 | 33-23-21 | D06022 | | | 8 | SM00118 | | | 9 | ALL |
| 0129AJ | 20 | GA | | | 10-0 | 35-21-21 | D06022 | | | 11 | SM00119 | | | 9 | ALL |
| 0130K | 18 | GA | | | 10-0 | 35-21-21 | D06022 | | | 10 | SM00120 | | | 9 | ALL |
| 0131G | 16 | GA | | | 10-0 | 33-24-21 | D06024 | | | 1 | SM00131 | | | 9 | ALL |
| 0132WV | 22 | GA | | | 10-0 | 33-25-21 | D06024 | | | 2 | SM00132 | | | 9 | ALL |
| 0133WG | 22 | GA | | | 10-0 | 33-25-21 | D06024 | | | 3 | SM00133 | | | 9 | ALL |
| 0134WO | 22 | GA | | | 10-0 | 33-25-21 | D06024 | | | 4 | SM00134 | | | 9 | ALL |
| 0135V | 22 | GA | | | 10-0 | 33-25-21 | D06024 | | | 5 | SM00135 | | | 9 | ALL |
| 0136WN | 16 | GA | | | 10-0 | 33-23-21 | D06024 | | | 6 | SM00136 | | | 9 | ALL |
| 0137W | 20 | GA | | | 10-0 | 33-24-21 | D06024 | | | 7 | SM00137 | | | 9 | ALL |
| 0138WP | 16 | GA | | | 10-0 | 33-23-21 | D06024 | | | 8 | SM00138 | | | 9 | ALL |
| 0139AJ | 20 | GA | | | 10-0 | 35-21-21 | D06024 | | | 11 | SM00139 | | | 9 | ALL |
| 0140K | 18 | GA | | | 10-0 | 35-21-21 | D06024 | | | 10 | SM00140 | | | 9 | ALL |
| 0141G | 16 | GA | | | 11-0 | 33-24-21 | D06026 | | | 1 | SM00131 | | | 9 | ALL |
| 0142WV | 22 | GA | | | 11-0 | 33-25-21 | D06026 | | | 2 | SM00132 | | | 9 | ALL |
| 0143WG | 22 | GA | | | 11-0 | 33-25-21 | D06026 | | | 3 | SM00133 | | | 9 | ALL |
| 0144WO | 22 | GA | | | 11-0 | 33-25-21 | D06026 | | | 4 | SM00134 | | | 9 | ALL |
| 0145V | 22 | GA | | | 11-0 | 33-25-21 | D06026 | | | 5 | SM00135 | | | 9 | ALL |
| 0146WN | 16 | GA | | | 11-0 | 33-23-21 | D06026 | | | 6 | SM00136 | | | 9 | ALL |
| 0147W | 20 | GA | | | 11-0 | 33-24-21 | D06026 | | | 7 | SM00137 | | | 9 | ALL |
| 0148WP | 16 | GA | | | 11-0 | 33-23-21 | D06026 | | | 8 | SM00138 | | | 9 | ALL |
| 0149AJ | 20 | GA | | | 11-0 | 35-21-21 | D06026 | | | 11 | SM00139 | | | 9 | ALL |
| 0150K | 18 | GA | | | 11-0 | 35-21-21 | D06026 | | | 10 | SM00140 | | | 9 | ALL |
| 0151G | 16 | GA | | | 9-0 | 33-24-21 | D06028 | | | 1 | SM00151 | | | 9 | ALL |
| 0152WV | 22 | GA | | | 9-0 | 33-25-21 | D06028 | | | 2 | SM00152 | | | 9 | ALL |
| 0153WG | 22 | GA | | | 9-0 | 33-25-21 | D06028 | | | 3 | SM00153 | | | 9 | ALL |
| 0154WO | 22 | GA | | | 9-0 | 33-25-21 | D06028 | | | 4 | SM00154 | | | 9 | ALL |
| 0155V | 22 | GA | | | 9-0 | 33-25-21 | D06028 | | | 5 | SM00155 | | | 9 | ALL |
| 0156WN | 16 | GA | | | 9-0 | 33-23-21 | D06028 | | | 6 | SM00156 | | | 9 | ALL |
| 0157W | 20 | GA | | | 9-0 | 33-24-21 | D06028 | | | 7 | SM00157 | | | 9 | ALL |
| 0158WP | 16 | GA | | | 9-0 | 33-23-21 | D06028 | | | 8 | SM00158 | | | 9 | ALL |
| 0159AJ | 20 | GA | | | 9-0 | 35-21-21 | D06028 | | | 11 | SM00159 | | | 9 | ALL |
| 0160K | 18 | GA | | | 9-0 | 35-21-21 | D06028 | | | 10 | SM00160 | | | 9 | ALL |
| 0161G | 16 | GA | | | 9-0 | 33-24-21 | D06030 | | | 1 | SM00151 | | | 9 | ALL |
| 0162WV | 22 | GA | | | 9-0 | 33-25-21 | D06030 | | | 2 | SM00152 | | | 9 | ALL |
| 0163WG | 22 | GA | | | 9-0 | 33-25-21 | D06030 | | | 3 | SM00153 | | | 9 | ALL |
| 0164WO | 22 | GA | | | 9-0 | 33-25-21 | D06030 | | | 4 | SM00154 | | | 9 | ALL |
| 0165V | 22 | GA | | | 9-0 | 33-25-21 | D06030 | | | 5 | SM00155 | | | 9 | ALL |
| 0166WN | 16 | GA | | | 9-0 | 33-23-21 | D06030 | | | 6 | SM00156 | | | 9 | ALL |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | |
| 0167W | 20 | | GA | | 9-0 | 33-24-21 | | D06030 | | | | SM00157 | | 9 | | ALL |
| 0168WP | 16 | | GA | | 9-0 | 33-23-21 | | D06030 | | | | SM00158 | | 9 | | ALL |
| 0169AJ | 20 | | GA | | 9-0 | 35-21-21 | | D06030 | | | 11 | SM00159 | | 9 | | ALL |
| 0170K | 18 | | GA | | 9-0 | 35-21-21 | | D06030 | | | 10 | SM00160 | | 9 | | ALL |
| 0171G | 16 | | GA | | 4-0 | 33-24-21 | | D06032 | | | 1 | SM00171 | | 9 | | ALL |
| 0172WV | 22 | | GA | | 4-0 | 33-25-21 | | D06032 | | | 2 | SM00172 | | 9 | | ALL |
| 0173WG | 22 | | GA | | 4-0 | 33-25-21 | | D06032 | | | 3 | SM00173 | | 9 | | ALL |
| 0174WO | 22 | | GA | | 4-0 | 33-25-21 | | D06032 | | | 4 | SM00174 | | 9 | | ALL |
| 0175V | 22 | | GA | | 4-0 | 33-25-21 | | D06032 | | | 5 | SM00175 | | 9 | | ALL |
| 0176WN | 16 | | GA | | 4-0 | 33-23-22 | | D06032 | | | 6 | SM00176 | | 9 | | ALL |
| 0177W | 20 | | GA | | 4-0 | 33-24-21 | | D06032 | | | 7 | SM00177 | | 9 | | ALL |
| 0178WP | 16 | | GA | | 4-0 | 33-23-22 | | D06032 | | | 8 | SM00178 | | 9 | | ALL |
| 0179AJ | 20 | | GA | | 4-0 | 35-21-21 | | D06032 | | | 11 | SM00179 | | 9 | | ALL |
| 0180K | 18 | | GA | | 4-0 | 35-21-21 | | D06032 | | | 10 | SM00180 | | 9 | | ALL |
| 0181G | 16 | | GA | | 4-0 | 33-24-21 | | D06034 | | | 1 | SM00171 | | 9 | | ALL |
| 0182WV | 22 | | GA | | 4-0 | 33-25-21 | | D06034 | | | 2 | SM00172 | | 9 | | ALL |
| 0183WG | 22 | | GA | | 4-0 | 33-25-21 | | D06034 | | | 3 | SM00173 | | 9 | | ALL |
| 0184WO | 22 | | GA | | 4-0 | 33-25-21 | | D06034 | | | 4 | SM00174 | | 9 | | ALL |
| 0185V | 22 | | GA | | 4-0 | 33-25-21 | | D06034 | | | 5 | SM00175 | | 9 | | ALL |
| 0186WN | 16 | | GA | | 4-0 | 33-23-22 | | D06034 | | | 6 | SM00176 | | 9 | | ALL |
| 0187W | 20 | | GA | | 4-0 | 33-24-21 | | D06034 | | | 7 | SM00177 | | 9 | | ALL |
| 0188WP | 16 | | GA | | 4-0 | 33-23-22 | | D06034 | | | 8 | SM00178 | | 9 | | ALL |
| 0189AJ | 20 | | GA | | 4-0 | 35-21-21 | | D06034 | | | 11 | SM00179 | | 9 | | ALL |
| 0190K | 18 | | GA | | 4-0 | 35-21-21 | | D06034 | | | 10 | SM00180 | | 9 | | ALL |
| 0191G | 16 | | GA | | 8-0 | 33-24-21 | | D06036 | | | 1 | SM00191 | | 9 | | 001-099 |
| 0191G | 16 | | GA | | 9-0 | 33-24-21 | | D06036 | | | 1 | SM00191 | | 9 | | 115-199 |
| 0192WV | 22 | | GA | | 8-0 | 33-25-22 | | D06036 | | | 2 | SM00192 | | 9 | | 001-099 |
| 0192WV | 22 | | GA | | 9-0 | 33-25-22 | | D06036 | | | 2 | SM00192 | | 9 | | 115-199 |
| 0193WG | 22 | | GA | | 8-0 | 33-25-22 | | D06036 | | | 3 | SM00193 | | 9 | | 001-099 |
| 0193WG | 22 | | GA | | 9-0 | 33-25-22 | | D06036 | | | 3 | SM00193 | | 9 | | 115-199 |
| 0194WO | 22 | | GA | | 8-0 | 33-25-22 | | D06036 | | | 4 | SM00194 | | 9 | | 001-099 |
| 0194WO | 22 | | GA | | 9-0 | 33-25-22 | | D06036 | | | 4 | SM00194 | | 9 | | 115-199 |
| 0195V | 22 | | GA | | 8-0 | 33-25-22 | | D06036 | | | 5 | SM00195 | | 9 | | 001-099 |
| 0195V | 22 | | GA | | 9-0 | 33-25-22 | | D06036 | | | 5 | SM00195 | | 9 | | 115-199 |
| 0196WN | 16 | | GA | | 8-0 | 33-23-22 | | D06036 | | | 6 | SM00196 | | 9 | | 001-099 |
| 0196WN | 16 | | GA | | 9-0 | 33-23-22 | | D06036 | | | 6 | SM00196 | | 9 | | 115-199 |
| 0197W | 20 | | GA | | 8-0 | 33-24-21 | | D06036 | | | 7 | SM00197 | | 9 | | 001-099 |
| 0197W | 20 | | GA | | 9-0 | 33-24-21 | | D06036 | | | 7 | SM00197 | | 9 | | 115-199 |
| 0198WP | 16 | | GA | | 8-0 | 33-23-22 | | D06036 | | | 8 | SM00198 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | |
| 0198WP | 16 | | GA | | 9-0 | 33-23-22 | D06036 | | | 8 | SM00198 | | | 9 | 115-199 |
| 0199AJ | 20 | | GA | | 8-0 | 35-21-21 | D06036 | | | 11 | SM00199 | | | 9 | 001-099 |
| 0199AJ | 20 | | GA | | 9-0 | 35-21-21 | D06036 | | | 11 | SM00199 | | | 9 | 115-199 |
| 0200K | 18 | | GA | | 8-0 | 35-21-21 | D06036 | | | 10 | SM00200 | | | 9 | 001-099 |
| 0200K | 18 | | GA | | 9-0 | 35-21-21 | D06036 | | | 10 | SM00200 | | | 9 | 115-199 |
| 0201G | 16 | | GA | | 8-0 | 33-24-21 | D06038 | | | 1 | SM00191 | | | 9 | ALL |
| 0202WV | 22 | | GA | | 8-0 | 33-25-22 | D06038 | | | 2 | SM00192 | | | 9 | ALL |
| 0203WG | 22 | | GA | | 8-0 | 33-25-22 | D06038 | | | 3 | SM00193 | | | 9 | ALL |
| 0204WO | 22 | | GA | | 8-0 | 33-25-22 | D06038 | | | 4 | SM00194 | | | 9 | ALL |
| 0205V | 22 | | GA | | 8-0 | 33-25-22 | D06038 | | | 5 | SM00195 | | | 9 | ALL |
| 0206WN | 16 | | GA | | 8-0 | 33-23-22 | D06038 | | | 6 | SM00196 | | | 9 | ALL |
| 0207W | 20 | | GA | | 8-0 | 33-24-21 | D06038 | | | 7 | SM00197 | | | 9 | ALL |
| 0208WP | 16 | | GA | | 8-0 | 33-23-22 | D06038 | | | 8 | SM00198 | | | 9 | ALL |
| 0209AJ | 20 | | GA | | 8-0 | 35-21-21 | D06038 | | | 11 | SM00199 | | | 9 | ALL |
| 0210K | 18 | | GA | | 8-0 | 35-21-21 | D06038 | | | 10 | SM00200 | | | 9 | ALL |
| 0211G | 16 | | GA | | 9-0 | 33-24-21 | D06040 | | | 1 | SM00191 | | | 9 | ALL |
| 0212WV | 22 | | GA | | 9-0 | 33-25-22 | D06040 | | | 2 | SM00192 | | | 9 | ALL |
| 0213WG | 22 | | GA | | 9-0 | 33-25-22 | D06040 | | | 3 | SM00193 | | | 9 | ALL |
| 0214WO | 22 | | GA | | 9-0 | 33-25-22 | D06040 | | | 4 | SM00194 | | | 9 | ALL |
| 0215V | 22 | | GA | | 9-0 | 33-25-22 | D06040 | | | 5 | SM00195 | | | 9 | ALL |
| 0216WN | 16 | | GA | | 9-0 | 33-23-22 | D06040 | | | 6 | SM00196 | | | 9 | ALL |
| 0217W | 20 | | GA | | 9-0 | 33-24-21 | D06040 | | | 7 | SM00197 | | | 9 | ALL |
| 0218WP | 16 | | GA | | 9-0 | 33-23-22 | D06040 | | | 8 | SM00198 | | | 9 | ALL |
| 0219AJ | 20 | | GA | | 9-0 | 35-21-21 | D06040 | | | 11 | SM00199 | | | 9 | ALL |
| 0220K | 18 | | GA | | 9-0 | 35-21-21 | D06040 | | | 10 | SM00200 | | | 9 | ALL |
| 0221G | 16 | | GA | | 8-0 | 33-24-21 | D06042 | | | 1 | SM00231 | | | 9 | ALL |
| 0222WV | 22 | | GA | | 8-0 | 33-25-22 | D06042 | | | 2 | SM00232 | | | 9 | ALL |
| 0223WG | 22 | | GA | | 8-0 | 33-25-22 | D06042 | | | 3 | SM00233 | | | 9 | ALL |
| 0224WO | 22 | | GA | | 8-0 | 33-25-22 | D06042 | | | 4 | SM00234 | | | 9 | ALL |
| 0225V | 22 | | GA | | 8-0 | 33-25-22 | D06042 | | | 5 | SM00235 | | | 9 | ALL |
| 0226WN | 16 | | GA | | 8-0 | 33-23-22 | D06042 | | | 6 | SM00236 | | | 9 | ALL |
| 0227W | 20 | | GA | | 8-0 | 33-24-21 | D06042 | | | 7 | SM00237 | | | 9 | ALL |
| 0228WP | 16 | | GA | | 8-0 | 33-23-22 | D06042 | | | 8 | SM00238 | | | 9 | ALL |
| 0229AJ | 20 | | GA | | 8-0 | 35-21-21 | D06042 | | | 11 | SM00239 | | | 9 | ALL |
| 0230K | 18 | | GA | | 8-0 | 35-21-21 | D06042 | | | 10 | SM00240 | | | 9 | ALL |
| 0231G | 16 | | GA | | 9-0 | 33-24-21 | D06044 | | | 1 | SM00231 | | | 9 | ALL |
| 0232WV | 22 | | GA | | 9-0 | 33-25-22 | D06044 | | | 2 | SM00232 | | | 9 | ALL |
| 0233WG | 22 | | GA | | 9-0 | 33-25-22 | D06044 | | | 3 | SM00233 | | | 9 | ALL |
| 0234WO | 22 | | GA | | 9-0 | 33-25-22 | D06044 | | | 4 | SM00234 | | | 9 | ALL |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | |
| 0235V | 22 | | GA | | 9-0 | 33-25-22 | | D06044 | | 5 | | SM00235 | | 9 | | ALL |
| 0236WN | 16 | | GA | | 9-0 | 33-23-22 | | D06044 | | 6 | | SM00236 | | 9 | | ALL |
| 0237W | 20 | | GA | | 9-0 | 33-24-21 | | D06044 | | 7 | | SM00237 | | 9 | | ALL |
| 0238WP | 16 | | GA | | 9-0 | 33-23-22 | | D06044 | | 8 | | SM00238 | | 9 | | ALL |
| 0239AJ | 20 | | GA | | 9-0 | 35-21-21 | | D06044 | | 11 | | SM00239 | | 9 | | ALL |
| 0240K | 18 | | GA | | 9-0 | 35-21-21 | | D06044 | | 10 | | SM00240 | | 9 | | ALL |
| 0241G | 16 | | GA | | 8-0 | 33-24-21 | | D05872 | | 1 | | SM00251 | | 9 | | ALL |
| 0242WV | 22 | | GA | | 8-0 | 33-25-22 | | D05872 | | 2 | | SM00252 | | 9 | | ALL |
| 0243WG | 22 | | GA | | 8-0 | 33-25-22 | | D05872 | | 3 | | SM00253 | | 9 | | ALL |
| 0244WO | 22 | | GA | | 8-0 | 33-25-22 | | D05872 | | 4 | | SM00254 | | 9 | | ALL |
| 0245V | 22 | | GA | | 8-0 | 33-25-22 | | D05872 | | 5 | | SM00255 | | 9 | | ALL |
| 0246WN | 16 | | GA | | 8-0 | 33-23-22 | | D05872 | | 6 | | SM00256 | | 9 | | ALL |
| 0247W | 20 | | GA | | 8-0 | 33-24-21 | | D05872 | | 7 | | SM00257 | | 9 | | ALL |
| 0248WP | 16 | | GA | | 8-0 | 33-23-22 | | D05872 | | 8 | | SM00258 | | 9 | | ALL |
| 0249AJ | 20 | | GA | | 8-0 | 35-21-21 | | D05872 | | 11 | | SM00259 | | 9 | | ALL |
| 0250K | 18 | | GA | | 8-0 | 35-21-21 | | D05872 | | 10 | | SM00260 | | 9 | | ALL |
| 0251G | 16 | | GA | | 11-0 | 33-24-21 | | D05874 | | 1 | | SM00251 | | 9 | | ALL |
| 0252WV | 22 | | GA | | 11-0 | 33-25-22 | | D05874 | | 2 | | SM00252 | | 9 | | ALL |
| 0253WG | 22 | | GA | | 11-0 | 33-25-22 | | D05874 | | 3 | | SM00253 | | 9 | | ALL |
| 0254WO | 22 | | GA | | 11-0 | 33-25-22 | | D05874 | | 4 | | SM00254 | | 9 | | ALL |
| 0255V | 22 | | GA | | 11-0 | 33-25-22 | | D05874 | | 5 | | SM00255 | | 9 | | ALL |
| 0256WN | 16 | | GA | | 11-0 | 33-23-22 | | D05874 | | 6 | | SM00256 | | 9 | | ALL |
| 0257W | 20 | | GA | | 11-0 | 33-24-21 | | D05874 | | 7 | | SM00257 | | 9 | | ALL |
| 0258WP | 16 | | GA | | 11-0 | 33-23-22 | | D05874 | | 8 | | SM00258 | | 9 | | ALL |
| 0259AJ | 20 | | GA | | 11-0 | 35-21-21 | | D05874 | | 11 | | SM00259 | | 9 | | ALL |
| 0260K | 18 | | GA | | 11-0 | 35-21-21 | | D05874 | | 10 | | SM00260 | | 9 | | ALL |
| 0411G | 16 | | GA | | 4-0 | 33-24-21 | | SM00011 | | | 9 | SM00031 | | 9 | | ALL |
| 0412WV | 22 | | GA | | 4-0 | 33-25-21 | | SM00012 | | | 9 | SM00032 | | 9 | | ALL |
| 0413WG | 22 | | GA | | 4-0 | 33-25-21 | | SM00013 | | | 9 | SM00033 | | 9 | | ALL |
| 0414WO | 22 | | GA | | 4-0 | 33-25-21 | | SM00014 | | | 9 | SM00034 | | 9 | | ALL |
| 0415V | 22 | | GA | | 4-0 | 33-25-21 | | SM00015 | | | 9 | SM00035 | | 9 | | ALL |
| 0416WN | 16 | | GA | | 4-0 | 33-23-21 | | SM00016 | | | 9 | SM00036 | | 9 | | ALL |
| 0417W | 20 | | GA | | 4-0 | 33-24-21 | | SM00017 | | | 9 | SM00037 | | 9 | | ALL |
| 0418WP | 16 | | GA | | 4-0 | 33-23-21 | | SM00018 | | | 9 | SM00038 | | 9 | | ALL |
| 0419AJ | 16 | | GA | | 4-0 | 35-21-21 | | SM00019 | | | 9 | SM00039 | | 9 | | ALL |
| 0420K | 18 | | GA | | 4-0 | 35-21-21 | | SM00020 | | | 9 | SM00040 | | 9 | | ALL |
| 0431G | 16 | | GA | | 5-0 | 33-24-21 | | SM00031 | | | 9 | SM00051 | | 9 | | ALL |
| 0432WV | 22 | | GA | | 5-0 | 33-25-21 | | SM00032 | | | 9 | SM00052 | | 9 | | ALL |
| 0433WG | 22 | | GA | | 5-0 | 33-25-21 | | SM00033 | | | 9 | SM00053 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | |
| 0434WO | 22 | | GA | | 5-0 | 33-25-21 | SM00034 | | | 9 | SM00054 | | | 9 | ALL |
| 0435V | 22 | | GA | | 5-0 | 33-25-21 | SM00035 | | | 9 | SM00055 | | | 9 | ALL |
| 0436WN | 16 | | GA | | 5-0 | 33-23-21 | SM00036 | | | 9 | SM00056 | | | 9 | ALL |
| 0437W | 20 | | GA | | 5-0 | 33-24-21 | SM00037 | | | 9 | SM00057 | | | 9 | ALL |
| 0438WP | 16 | | GA | | 5-0 | 33-23-21 | SM00038 | | | 9 | SM00058 | | | 9 | ALL |
| 0439AJ | 16 | | GA | | 5-0 | 35-21-21 | SM00039 | | | 9 | SM00059 | | | 9 | ALL |
| 0440K | 18 | | GA | | 5-0 | 35-21-21 | SM00040 | | | 9 | SM00060 | | | 9 | ALL |
| 0451G | 16 | | GA | | 7-0 | 33-24-21 | SM00051 | | | 9 | SM00071 | | | 9 | ALL |
| 0452WV | 22 | | GA | | 5-0 | 33-25-21 | SM00052 | | | 9 | SM00072 | | | 9 | ALL |
| 0453WG | 22 | | GA | | 5-0 | 33-25-21 | SM00053 | | | 9 | SM00073 | | | 9 | ALL |
| 0454WO | 22 | | GA | | 5-0 | 33-25-21 | SM00054 | | | 9 | SM00074 | | | 9 | ALL |
| 0455V | 22 | | GA | | 5-0 | 33-25-21 | SM00055 | | | 9 | SM00075 | | | 9 | ALL |
| 0456WN | 16 | | GA | | 5-0 | 33-23-21 | SM00056 | | | 9 | SM00076 | | | 9 | ALL |
| 0457W | 20 | | GA | | 5-0 | 33-24-21 | SM00057 | | | 9 | SM00077 | | | 9 | ALL |
| 0458WP | 16 | | GA | | 5-0 | 33-23-21 | SM00058 | | | 9 | SM00078 | | | 9 | ALL |
| 0459AJ | 16 | | GA | | 5-0 | 35-21-21 | SM00059 | | | 9 | SM00079 | | | 9 | ALL |
| 0460K | 18 | | GA | | 5-0 | 35-21-21 | SM00060 | | | 9 | SM00080 | | | 9 | ALL |
| 0471G | 16 | | GA | | 2-0 | 33-24-21 | SM00071 | | | 9 | SM00091 | | | 9 | ALL |
| 0472WV | 22 | | GA | | 3-0 | 33-25-21 | SM00072 | | | 9 | SM00092 | | | 9 | ALL |
| 0473WG | 22 | | GA | | 3-0 | 33-25-21 | SM00073 | | | 9 | SM00093 | | | 9 | ALL |
| 0474WO | 22 | | GA | | 3-0 | 33-25-21 | SM00074 | | | 9 | SM00094 | | | 9 | ALL |
| 0475V | 22 | | GA | | 3-0 | 33-25-21 | SM00075 | | | 9 | SM00095 | | | 9 | ALL |
| 0476WN | 16 | | GA | | 3-0 | 33-23-21 | SM00076 | | | 9 | SM00096 | | | 9 | ALL |
| 0477W | 20 | | GA | | 3-0 | 33-24-21 | SM00077 | | | 9 | SM00097 | | | 9 | ALL |
| 0478WP | 16 | | GA | | 3-0 | 33-23-21 | SM00078 | | | 9 | SM00098 | | | 9 | ALL |
| 0479AJ | 16 | | GA | | 3-0 | 35-21-21 | SM00079 | | | 9 | SM00099 | | | 9 | ALL |
| 0480K | 18 | | GA | | 3-0 | 35-21-21 | SM00080 | | | 9 | SM00100 | | | 9 | ALL |
| 0491G | 16 | | GA | | 7-0 | 33-24-21 | SM00091 | | | 9 | SM00111 | | | 9 | ALL |
| 0492WV | 22 | | GA | | 7-0 | 33-25-21 | SM00092 | | | 9 | SM00112 | | | 9 | ALL |
| 0493WG | 22 | | GA | | 7-0 | 33-25-21 | SM00093 | | | 9 | SM00113 | | | 9 | ALL |
| 0494WO | 22 | | GA | | 7-0 | 33-25-21 | SM00094 | | | 9 | SM00114 | | | 9 | ALL |
| 0495V | 22 | | GA | | 7-0 | 33-25-21 | SM00095 | | | 9 | SM00115 | | | 9 | ALL |
| 0496WN | 16 | | GA | | 7-0 | 33-23-21 | SM00096 | | | 9 | SM00116 | | | 9 | ALL |
| 0497W | 20 | | GA | | 7-0 | 33-24-21 | SM00097 | | | 9 | SM00117 | | | 9 | ALL |
| 0498WP | 16 | | GA | | 7-0 | 33-23-21 | SM00098 | | | 9 | SM00118 | | | 9 | ALL |
| 0499AJ | 16 | | GA | | 7-0 | 35-21-21 | SM00099 | | | 9 | SM00119 | | | 9 | ALL |
| 0500K | 18 | | GA | | 7-0 | 35-21-21 | SM00100 | | | 9 | SM00120 | | | 9 | ALL |
| 0511G | 16 | | GA | | 4-0 | 33-24-21 | SM00111 | | | 9 | SM00131 | | | 9 | ALL |
| 0512WV | 22 | | GA | | 4-0 | 33-25-21 | SM00112 | | | 9 | SM00132 | | | 9 | ALL |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | |
| 0513WG | 22 | | GA | | 4-0 | 33-25-21 | | SM00113 | | | | SM00133 | | 9 | | ALL |
| 0514WO | 22 | | GA | | 4-0 | 33-25-21 | | SM00114 | | | | SM00134 | | 9 | | ALL |
| 0515V | 22 | | GA | | 4-0 | 33-25-21 | | SM00115 | | | | SM00135 | | 9 | | ALL |
| 0516WN | 16 | | GA | | 4-0 | 33-23-21 | | SM00116 | | | | SM00136 | | 9 | | ALL |
| 0517W | 20 | | GA | | 4-0 | 33-24-21 | | SM00117 | | | | SM00137 | | 9 | | ALL |
| 0518WP | 16 | | GA | | 4-0 | 33-23-21 | | SM00118 | | | | SM00138 | | 9 | | ALL |
| 0519AJ | 16 | | GA | | 4-0 | 35-21-21 | | SM00119 | | | | SM00139 | | 9 | | ALL |
| 0520K | 18 | | GA | | 4-0 | 35-21-21 | | SM00120 | | | | SM00140 | | 9 | | ALL |
| 0531G | 16 | | GA | | 7-0 | 33-24-21 | | SM00131 | | | | SM00151 | | 9 | | ALL |
| 0532WV | 22 | | GA | | 7-0 | 33-25-21 | | SM00132 | | | | SM00152 | | 9 | | ALL |
| 0533WG | 22 | | GA | | 7-0 | 33-25-21 | | SM00133 | | | | SM00153 | | 9 | | ALL |
| 0534WO | 22 | | GA | | 7-0 | 33-25-21 | | SM00134 | | | | SM00154 | | 9 | | ALL |
| 0535V | 22 | | GA | | 7-0 | 33-25-21 | | SM00135 | | | | SM00155 | | 9 | | ALL |
| 0536WN | 16 | | GA | | 7-0 | 33-23-21 | | SM00136 | | | | SM00156 | | 9 | | ALL |
| 0537W | 20 | | GA | | 7-0 | 33-24-21 | | SM00137 | | | | SM00157 | | 9 | | ALL |
| 0538WP | 16 | | GA | | 7-0 | 33-23-21 | | SM00138 | | | | SM00158 | | 9 | | ALL |
| 0539AJ | 16 | | GA | | 7-0 | 35-21-21 | | SM00139 | | | | SM00159 | | 9 | | ALL |
| 0540K | 18 | | GA | | 7-0 | 35-21-21 | | SM00140 | | | | SM00160 | | 9 | | ALL |
| 0551G | 16 | | GA | | 8-0 | 33-24-21 | | SM00151 | | | | SM00171 | | 9 | | 001-099 |
| 0551G | 16 | | GA | | 7-0 | 33-24-21 | | SM00151 | | | | SM00171 | | 9 | | 115-199 |
| 0552WV | 22 | | GA | | 8-0 | 33-25-21 | | SM00152 | | | | SM00172 | | 9 | | 001-099 |
| 0552WV | 22 | | GA | | 7-0 | 33-25-21 | | SM00152 | | | | SM00172 | | 9 | | 115-199 |
| 0553WG | 22 | | GA | | 8-0 | 33-25-21 | | SM00153 | | | | SM00173 | | 9 | | 001-099 |
| 0553WG | 22 | | GA | | 7-0 | 33-25-21 | | SM00153 | | | | SM00173 | | 9 | | 115-199 |
| 0554WO | 22 | | GA | | 8-0 | 33-25-21 | | SM00154 | | | | SM00174 | | 9 | | 001-099 |
| 0554WO | 22 | | GA | | 7-0 | 33-25-21 | | SM00154 | | | | SM00174 | | 9 | | 115-199 |
| 0555V | 22 | | GA | | 8-0 | 33-25-21 | | SM00155 | | | | SM00175 | | 9 | | 001-099 |
| 0555V | 22 | | GA | | 7-0 | 33-25-21 | | SM00155 | | | | SM00175 | | 9 | | 115-199 |
| 0557W | 20 | | GA | | 8-0 | 33-24-21 | | SM00157 | | | | SM00177 | | 9 | | 001-099 |
| 0557W | 20 | | GA | | 7-0 | 33-24-21 | | SM00157 | | | | SM00177 | | 9 | | 115-199 |
| 0558WP | 16 | | GA | | 8-0 | 33-23-21 | | SM00158 | | | | SM00178 | | 9 | | 001-099 |
| 0558WP | 16 | | GA | | 7-0 | 33-23-21 | | SM00158 | | | | SM00178 | | 9 | | 115-199 |
| 0559AJ | 16 | | GA | | 8-0 | 35-21-21 | | SM00159 | | | | SM00179 | | 9 | | 001-099 |
| 0559AJ | 16 | | GA | | 7-0 | 35-21-21 | | SM00159 | | | | SM00179 | | 9 | | 115-199 |
| 0560K | 18 | | GA | | 8-0 | 35-21-21 | | SM00160 | | | | SM00180 | | 9 | | 001-099 |
| 0560K | 18 | | GA | | 7-0 | 35-21-21 | | SM00160 | | | | SM00180 | | 9 | | 115-199 |
| 0571G | 16 | | GA | | 5-0 | 33-24-21 | | SM00171 | | | | SM00191 | | 9 | | ALL |
| 0572WV | 22 | | GA | | 5-0 | 33-25-21 | | SM00172 | | | | SM00192 | | 9 | | ALL |
| 0573WG | 22 | | GA | | 5-0 | 33-25-21 | | SM00173 | | | | SM00193 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | |
| 0574WO | 22 | GA | | | 5-0 | 33-25-21 | SM00174 | | | 9 | SM00194 | | | 9 | ALL |
| 0575V | 22 | GA | | | 5-0 | 33-25-21 | SM00175 | | | 9 | SM00195 | | | 9 | ALL |
| 0576WN | 16 | GA | | | 5-0 | 33-23-22 | SM00176 | | | 9 | SM00196 | | | 9 | ALL |
| 0577W | 20 | GA | | | 5-0 | 33-24-21 | SM00177 | | | 9 | SM00197 | | | 9 | ALL |
| 0578WP | 16 | GA | | | 5-0 | 33-23-22 | SM00178 | | | 9 | SM00198 | | | 9 | ALL |
| 0579AJ | 16 | GA | | | 5-0 | 35-21-21 | SM00179 | | | 9 | SM00199 | | | 9 | ALL |
| 0580K | 18 | GA | | | 5-0 | 35-21-21 | SM00180 | | | 9 | SM00200 | | | 9 | ALL |
| 0591G | 16 | GA | | | 5-0 | 33-24-21 | SM00191 | | | 9 | SM00231 | | | 9 | ALL |
| 0592WV | 22 | GA | | | 5-0 | 33-25-22 | SM00192 | | | 9 | SM00232 | | | 9 | ALL |
| 0593WG | 22 | GA | | | 5-0 | 33-25-22 | SM00193 | | | 9 | SM00233 | | | 9 | ALL |
| 0594WO | 22 | GA | | | 5-0 | 33-25-22 | SM00194 | | | 9 | SM00234 | | | 9 | ALL |
| 0595V | 22 | GA | | | 5-0 | 33-25-22 | SM00195 | | | 9 | SM00235 | | | 9 | ALL |
| 0596WN | 16 | GA | | | 5-0 | 33-23-22 | SM00196 | | | 9 | SM00236 | | | 9 | ALL |
| 0597W | 20 | GA | | | 5-0 | 33-24-21 | SM00197 | | | 9 | SM00237 | | | 9 | ALL |
| 0598WP | 16 | GA | | | 5-0 | 33-23-22 | SM00198 | | | 9 | SM00238 | | | 9 | ALL |
| 0599AJ | 16 | GA | | | 5-0 | 35-21-21 | SM00199 | | | 9 | SM00239 | | | 9 | ALL |
| 0600K | 18 | GA | | | 5-0 | 35-21-21 | SM00200 | | | 9 | SM00240 | | | 9 | ALL |
| 0631G | 16 | GA | | | 8-0 | 33-24-21 | SM00231 | | | 9 | SM00251 | | | 9 | 001-099 |
| 0631G | 16 | GA | | | 7-0 | 33-24-21 | SM00231 | | | 9 | SM00251 | | | 9 | 115-199 |
| 0632WV | 22 | GA | | | 8-0 | 33-25-22 | SM00232 | | | 9 | SM00252 | | | 9 | 001-099 |
| 0632WV | 22 | GA | | | 7-0 | 33-25-22 | SM00232 | | | 9 | SM00252 | | | 9 | 115-199 |
| 0633WG | 22 | GA | | | 8-0 | 33-25-22 | SM00233 | | | 9 | SM00253 | | | 9 | 001-099 |
| 0633WG | 22 | GA | | | 7-0 | 33-25-22 | SM00233 | | | 9 | SM00253 | | | 9 | 115-199 |
| 0634WO | 22 | GA | | | 8-0 | 33-25-22 | SM00234 | | | 9 | SM00254 | | | 9 | 001-099 |
| 0634WO | 22 | GA | | | 7-0 | 33-25-22 | SM00234 | | | 9 | SM00254 | | | 9 | 115-199 |
| 0635V | 22 | GA | | | 8-0 | 33-25-22 | SM00235 | | | 9 | SM00255 | | | 9 | 001-099 |
| 0635V | 22 | GA | | | 7-0 | 33-25-22 | SM00235 | | | 9 | SM00255 | | | 9 | 115-199 |
| 0636WN | 16 | GA | | | 8-0 | 33-23-22 | SM00236 | | | 9 | SM00256 | | | 9 | 001-099 |
| 0636WN | 16 | GA | | | 7-0 | 33-23-22 | SM00236 | | | 9 | SM00256 | | | 9 | 115-199 |
| 0637W | 20 | GA | | | 8-0 | 33-24-21 | SM00237 | | | 9 | SM00257 | | | 9 | 001-099 |
| 0637W | 20 | GA | | | 7-0 | 33-24-21 | SM00237 | | | 9 | SM00257 | | | 9 | 115-199 |
| 0638WP | 16 | GA | | | 8-0 | 33-23-22 | SM00238 | | | 9 | SM00258 | | | 9 | 001-099 |
| 0638WP | 16 | GA | | | 7-0 | 33-23-22 | SM00238 | | | 9 | SM00258 | | | 9 | 115-199 |
| 0639AJ | 16 | GA | | | 8-0 | 35-21-21 | SM00239 | | | 9 | SM00259 | | | 9 | 001-099 |
| 0639AJ | 16 | GA | | | 7-0 | 35-21-21 | SM00239 | | | 9 | SM00259 | | | 9 | 115-199 |
| 0640K | 18 | GA | | | 8-0 | 35-21-21 | SM00240 | | | 9 | SM00260 | | | 9 | 001-099 |
| 0640K | 18 | GA | | | 7-0 | 35-21-21 | SM00240 | | | 9 | SM00260 | | | 9 | 115-199 |
| 0801 | 16 | GA | | | 24-0 | 33-24-21 | D40410P | | 1 | 16 | SM00071 | | | 9 | ALL |
| 0802 | 22 | GA | | | 25-0 | 33-25-21 | D40410P | | 2 | | SM00072 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 10

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | |
| 0805 | 22 | | GA | | 13-0 | 33-25-21 | | SP00006 | | | 9 | SM00075 | | | 9 | ALL |
| 0807 | 20 | | GA | | 25-0 | 33-24-21 | | D40410P | | 7 | | SM00077 | | | 9 | ALL |
| 0809 | 16 | | GA | | 25-0 | 35-21-21 | | D40410P | | 31 | 16 | SM00079 | | | 9 | ALL |
| 0811 | 16 | | GA | | 7-0 | 33-24-21 | | SM00251 | | | 9 | D40412J | | 1 | | 001-099 |
| 0811 | 16 | | GA | | 8-0 | 33-24-21 | | SM00251 | | | 9 | D40412J | | 1 | | 115-199 |
| 0812 | 22 | | GA | | 7-0 | 33-25-22 | | SM00252 | | | 9 | D40412J | | 2 | | 001-099 |
| 0812 | 22 | | GA | | 8-0 | 33-25-22 | | SM00252 | | | 9 | D40412J | | 2 | | 115-199 |
| 0813 | 22 | | GA | | 7-0 | 33-25-22 | | SM00253 | | | 9 | D40412J | | 3 | | 001-099 |
| 0813 | 22 | | GA | | 8-0 | 33-25-22 | | SM00253 | | | 9 | D40412J | | 3 | | 115-199 |
| 0814 | 22 | | GA | | 7-0 | 33-25-22 | | SM00254 | | | 9 | D40412J | | 4 | | 001-099 |
| 0814 | 22 | | GA | | 8-0 | 33-25-22 | | SM00254 | | | 9 | D40412J | | 4 | | 115-199 |
| 0815 | 22 | | GA | | 7-0 | 33-25-22 | | SM00255 | | | 9 | D40412J | | 5 | | 001-099 |
| 0815 | 22 | | GA | | 8-0 | 33-25-22 | | SM00255 | | | 9 | D40412J | | 5 | | 115-199 |
| 0817 | 20 | | GA | | 7-0 | 33-24-21 | | SM00257 | | | 9 | D40412J | | 7 | | 001-099 |
| 0817 | 20 | | GA | | 8-0 | 33-24-21 | | SM00257 | | | 9 | D40412J | | 7 | | 115-199 |
| 0822 | 16 | | GA | | 60-0 | SPARE | | D40410P | | 22 | 16 | D40412J | | 22 | | 001-099 |
| 0822 | 16 | | GA | | 59-0 | SPARE | | D40410P | | 22 | 16 | D40412J | | 22 | | 115-199 |
| 0825 | 22 | | GA | | 49-0 | 33-25-23 | | SP00006 | | | 9 | D40412J | | 25 | | 001-099 |
| 0825 | 22 | | GA | | 48-0 | 33-25-23 | | SP00006 | | | 9 | D40412J | | 25 | | 115-199 |
| 0827 | 20 | | GA | | 60-0 | 33-23-23 | | D40410P | | 27 | | D40412J | | 27 | | 001-099 |
| 0827 | 20 | | GA | | 59-0 | 33-23-23 | | D40410P | | 27 | | D40412J | | 27 | | 115-199 |
| 0828 | 20 | | GA | | 60-0 | 33-23-24 | | D40410P | | 28 | | D40412J | | 28 | | 001-099 |
| 0828 | 20 | | GA | | 59-0 | 33-23-24 | | D40410P | | 28 | | D40412J | | 28 | | 115-199 |
| 0829 | 16 | | GA | | 60-0 | 35-21-22 | | D40410P | | 29 | 16 | D40412J | | 29 | | 001-099 |
| 0829 | 16 | | GA | | 59-0 | 35-21-22 | | D40410P | | 29 | 16 | D40412J | | 29 | | 115-199 |
| 0835 | 22 | | GA | | 60-0 | 23-31-41 | | D40410P | | 15 | | D40412J | | 15 | | 001-099 |
| 0835 | 22 | | GA | | 59-0 | 23-31-41 | | D40410P | | 15 | | D40412J | | 15 | | 115-199 |
| 0836 | 16 | | GA | | 7-0 | 33-23-22 | | SM00256 | | | 9 | D40412J | | 36 | | 001-099 |
| 0836 | 16 | | GA | | 8-0 | 33-23-22 | | SM00256 | | | 9 | D40412J | | 36 | | 115-199 |
| 0838 | 16 | | GA | | 7-0 | 33-23-22 | | SM00258 | | | 9 | D40412J | | 38 | | 001-099 |
| 0838 | 16 | | GA | | 8-0 | 33-23-22 | | SM00258 | | | 9 | D40412J | | 38 | | 115-199 |
| 0839 | 16 | | GA | | 7-0 | 35-21-21 | | SM00259 | | | 9 | D40412J | | 39 | | 001-099 |
| 0839 | 16 | | GA | | 8-0 | 35-21-21 | | SM00259 | | | 9 | D40412J | | 39 | | 115-199 |
| 0840 | 18 | | GA | | 7-0 | 35-21-21 | | SM00260 | | | 9 | D40412J | | 40 | | 001-099 |
| 0840 | 18 | | GA | | 8-0 | 35-21-21 | | SM00260 | | | 9 | D40412J | | 40 | | 115-199 |
| 0845 | 22 | | GA | | 42-0 | SPARE | | D40410P | | 5 | | D01241 | | 3 | | ALL |
| 0854 | 14 | | GA | | 8-0 | 33-23-21 | | T10052 | | GND | E | GD03191 | | AC.. | E | 001-099 |
| 0854 | 14 | | GA | | 6-0 | 33-23-21 | | T10052 | | GND | E | GD03191 | | AC.. | E | 115-199 |
| 0855 | 20 | | GA | | 28-0 | 33-23-21 | | D40410P | | | 25 | T10052 | | HV3 | E | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 11

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity | | | | |
|------------|-------------|--|---------|----------|------------------|-------|------------------|-------------|---------|
| Wire No. | GA CO TY | Fam | Diagram | Equip | Term Type Splice | Equip | Term Type Splice | Effectivity | |
| W3802 | 286N3802 | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | |
| 0855 | 20 | GA | 26-0 | 33-23-21 | D40410P | 25 | T10052 | HV3 E | 115-199 |
| 0856 | 16 | GA | 6-0 | 33-23-21 | T10052 | LV E | SM00076 | 9 | 001-099 |
| 0856 | 16 | GA | 7-0 | 33-23-21 | T10052 | LV E | SM00076 | 9 | 115-199 |
| 0861 | 14 | GA | 7-0 | 33-23-22 | T10016 | GND E | GD03189 | AC.. E | ALL |
| 0865 | 20 | GA | 53-0 | 33-23-22 | D40410P | 26 | T10016 | HV3 E | 001-099 |
| 0865 | 20 | GA | 51-0 | 33-23-22 | D40410P | 26 | T10016 | HV3 E | 115-199 |
| 0866 | 16 | GA | 7-0 | 33-23-22 | T10016 | LV E | SM00236 | 9 | ALL |
| 0904 | 16 | GA | 9-0 | 33-24-21 | D41352J | 1 VY | SM00151 | 9 | 001-099 |
| 0904 | 16 | GA | 8-0 | 33-24-21 | D06318 | 1 | SM00151 | 9 | 115-199 |
| 0905 | 20 | GA | 9-0 | 33-24-21 | D41348J | 1 VS | SM00157 | 9 | 001-099 |
| 0905 | 20 | GA | 8-0 | 33-24-21 | D06318 | 7 | SM00157 | 9 | 115-199 |
| 0906 | 16 | GA | 10-0 | 33-24-21 | D41350P | 1 VG | GD03287 | AC.. E | 001-099 |
| 0906 | 16 | GA | 8-0 | 33-24-21 | D06318 | 8 | GD03287 | AC.. E | 115-199 |
| 0908 | 16 | GA | 3-0 | 33-23-21 | SM00018 | 9 | GD03193 | AC.. E | ALL |
| 0909 | 16 | GA | 11-0 | 33-24-21 | D41438J | 1 VY | SM00171 | 9 | 001-099 |
| 0909 | 16 | GA | 15-0 | 33-24-21 | SM00171 | 9 | D06330 | 1 | 115-199 |
| 0910 | 18 | GA | 4-0 | 35-21-21 | SM00020 | 9 | GD03195 | DC.. E | ALL |
| 0911 | 20 | GA | 60-0 | SPARE | D40410P | 11 | D40412J | 11 | 001-099 |
| 0911 | 20 | GA | 59-0 | SPARE | D40410P | 11 | D40412J | 11 | 115-199 |
| 0912 | 20 | GA | 11-0 | 33-24-21 | D41434J | 1 VS | SM00177 | 9 | 001-099 |
| 0912 | 20 | GA | 15-0 | 33-24-21 | SM00177 | 9 | D06330 | 7 | 115-199 |
| 0913 | 16 | GA | 12-0 | 33-24-21 | D41436P | 1 VG | GD03289 | AC.. E | 001-099 |
| 0913 | 16 | GA | 5-0 | 33-24-21 | D06330 | 8 | GD03648 | AC.. E | 115-199 |
| 0918 | 16 | GA | 3-0 | 33-23-21 | SM00098 | 9 | GD03283 | AC.. E | ALL |
| 0920 | 18 | GA | 4-0 | 35-21-21 | SM00100 | 9 | GD03285 | DC.. E | 001-099 |
| 0920 | 18 | GA | 3-0 | 35-21-21 | SM00100 | 9 | GD03285 | DC.. E | 115-199 |
| 0921 | 16 | GA | 3-0 | 33-23-21 | SM00058 | 9 | GD03281 | AC.. E | ALL |
| 0922 | 16 | GA | 3-0 | 33-23-21 | SM00158 | 9 | GD03287 | AC.. E | 001-099 |
| 0922 | 16 | GA | 4-0 | 33-23-21 | SM00158 | 9 | GD03287 | AC.. E | 115-199 |
| 0923 | 16 | GA | 2-0 | 33-23-22 | SM00258 | 9 | GD03197 | AC.. E | ALL |
| 0928 | 16 | GA | 3-0 | 33-23-22 | SM00198 | 9 | GD03289 | AC.. E | ALL |
| 0930 | 18 | GA | 3-0 | 35-21-21 | SM00200 | 9 | GD03291 | DC.. E | ALL |
| 0942 | 22 | GA | 5-0 | 33-25-21 | SM00173 | 9 | SP00542 | 9 | ALL |
| 0952 | 22 | GA | 10-0 | 33-25-21 | SP00552 | 9 | SM00014 | 9 | 001-099 |
| 0962 | 22 | GA | 29-0 | 33-25-21 | SM06019 | 9 | SP01120 | 9 | 115-199 |
| 0963 | 22 | GA | 8-0 | 33-25-22 | SM06259 | 9 | D40412J | 9 | 115-199 |
| 0972 | 22 | GA | 7-0 | 33-25-21 | SM00154 | 9 | SP01124 | 9 | 115-199 |
| 0974 | 20 | GA | 9-0 | 23-31-31 | D01241 | 4 | SM00160 | 9 | 001-099 |
| 0974 | 20 | GA | 8-0 | 23-31-31 | D01241 | 4 | SM00160 | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 12

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | |
| 2011B | 22 | GB | B | | 12-0 | 23-31-31 | D06000 | 14 | | | SM00024 | | 9 | | 001-099 |
| 2011B | 22 | GB | B | | 13-0 | 23-31-31 | D06000 | 13 | | | SM00023 | | 9 | | 115-199 |
| 2011R | 22 | GB | B | | 0-0 | 23-31-31 | D06000 | 13 | | | SM00023 | | 9 | | 001-099 |
| 2011R | 22 | GB | B | | 0-0 | 23-31-31 | D06000 | 14 | | | SM00024 | | 9 | | 115-199 |
| 2021B | 22 | GB | C | | 12-0 | 23-31-31 | D06002 | 14 | | | SM00024 | | 9 | | 001-099 |
| 2021B | 22 | GB | C | | 12-0 | 23-31-31 | D06002 | 13 | | | SM00023 | | 9 | | 115-199 |
| 2021R | 22 | GB | C | | 0-0 | 23-31-31 | D06002 | 13 | | | SM00023 | | 9 | | 001-099 |
| 2021R | 22 | GB | C | | 0-0 | 23-31-31 | D06002 | 14 | | | SM00024 | | 9 | | 115-199 |
| 2023B | 22 | GB | D | | 4-0 | 23-31-31 | SM00024 | | 9 | | SM00044 | | 9 | | 001-099 |
| 2023B | 22 | GB | D | | 4-0 | 23-31-31 | SM00023 | | 9 | | SM00043 | | 9 | | 115-199 |
| 2023R | 22 | GB | D | | 0-0 | 23-31-31 | SM00023 | | 9 | | SM00043 | | 9 | | 001-099 |
| 2023R | 22 | GB | D | | 0-0 | 23-31-31 | SM00024 | | 9 | | SM00044 | | 9 | | 115-199 |
| 2031B | 22 | GB | E | | 8-0 | 23-31-31 | D06004 | 14 | | | SM00044 | | 9 | | 001-099 |
| 2031B | 22 | GB | E | | 8-0 | 23-31-31 | D06004 | 13 | | | SM00043 | | 9 | | 115-199 |
| 2031R | 22 | GB | E | | 0-0 | 23-31-31 | D06004 | 13 | | | SM00043 | | 9 | | 001-099 |
| 2031R | 22 | GB | E | | 0-0 | 23-31-31 | D06004 | 14 | | | SM00044 | | 9 | | 115-199 |
| 2041B | 22 | GB | F | | 10-0 | 23-31-31 | D06006 | 14 | | | SM00044 | | 9 | | 001-099 |
| 2041B | 22 | GB | F | | 10-0 | 23-31-31 | D06006 | 13 | | | SM00043 | | 9 | | 115-199 |
| 2041R | 22 | GB | F | | 0-0 | 23-31-31 | D06006 | 13 | | | SM00043 | | 9 | | 001-099 |
| 2041R | 22 | GB | F | | 0-0 | 23-31-31 | D06006 | 14 | | | SM00044 | | 9 | | 115-199 |
| 2043B | 22 | GB | G | | 5-0 | 23-31-31 | SM00044 | | 9 | | SM00064 | | 9 | | 001-099 |
| 2043B | 22 | GB | G | | 5-0 | 23-31-31 | SM00043 | | 9 | | SM00063 | | 9 | | 115-199 |
| 2043R | 22 | GB | G | | 0-0 | 23-31-31 | SM00043 | | 9 | | SM00063 | | 9 | | 001-099 |
| 2043R | 22 | GB | G | | 0-0 | 23-31-31 | SM00044 | | 9 | | SM00064 | | 9 | | 115-199 |
| 2051B | 22 | GB | H | | 8-0 | 23-31-31 | D06008 | 14 | | | SM00064 | | 9 | | 001-099 |
| 2051B | 22 | GB | H | | 8-0 | 23-31-31 | D06008 | 13 | | | SM00063 | | 9 | | 115-199 |
| 2051R | 22 | GB | H | | 0-0 | 23-31-31 | D06008 | 13 | | | SM00063 | | 9 | | 001-099 |
| 2051R | 22 | GB | H | | 0-0 | 23-31-31 | D06008 | 14 | | | SM00064 | | 9 | | 115-199 |
| 2061B | 22 | GB | I | | 11-0 | 23-31-31 | D06010 | 14 | | | SM00064 | | 9 | | 001-099 |
| 2061B | 22 | GB | I | | 11-0 | 23-31-31 | D06010 | 13 | | | SM00063 | | 9 | | 115-199 |
| 2061R | 22 | GB | I | | 0-0 | 23-31-31 | D06010 | 13 | | | SM00063 | | 9 | | 001-099 |
| 2061R | 22 | GB | I | | 0-0 | 23-31-31 | D06010 | 14 | | | SM00064 | | 9 | | 115-199 |
| 2063B | 22 | GB | J | | 5-0 | 23-31-31 | SM00064 | | 9 | | SM00084 | | 9 | | 001-099 |
| 2063B | 22 | GB | J | | 5-0 | 23-31-31 | SM00063 | | 9 | | SM00083 | | 9 | | 115-199 |
| 2063R | 22 | GB | J | | 0-0 | 23-31-31 | SM00063 | | 9 | | SM00083 | | 9 | | 001-099 |
| 2063R | 22 | GB | J | | 0-0 | 23-31-31 | SM00064 | | 9 | | SM00084 | | 9 | | 115-199 |
| 2071B | 22 | GB | K | | 8-0 | 23-31-31 | D06012 | 14 | | | SM00084 | | 9 | | 001-099 |
| 2071B | 22 | GB | K | | 9-0 | 23-31-31 | D06012 | 13 | | | SM00083 | | 9 | | 115-199 |
| 2071R | 22 | GB | K | | 0-0 | 23-31-31 | D06012 | 13 | | | SM00083 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 13

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | |
| 2071R | 22 | GB | K | | 0-0 | 23-31-31 | D06012 | 14 | | | SM00084 | | 9 | | 115-199 |
| 2081B | 22 | GB | L | | 9-0 | 23-31-31 | D06014 | 14 | | | SM00084 | | 9 | | 001-099 |
| 2081B | 22 | GB | L | | 10-0 | 23-31-31 | D06014 | 13 | | | SM00083 | | 9 | | 115-199 |
| 2081R | 22 | GB | L | | 0-0 | 23-31-31 | D06014 | 13 | | | SM00083 | | 9 | | 001-099 |
| 2081R | 22 | GB | L | | 0-0 | 23-31-31 | D06014 | 14 | | | SM00084 | | 9 | | 115-199 |
| 2083B | 22 | GB | M | | 3-0 | 23-31-31 | SM00084 | | 9 | | SM00104 | | 9 | | 001-099 |
| 2083B | 22 | GB | M | | 4-0 | 23-31-31 | SM00083 | | 9 | | SM00103 | | 9 | | 115-199 |
| 2083R | 22 | GB | M | | 0-0 | 23-31-31 | SM00083 | | 9 | | SM00103 | | 9 | | 001-099 |
| 2083R | 22 | GB | M | | 0-0 | 23-31-31 | SM00084 | | 9 | | SM00104 | | 9 | | 115-199 |
| 2091B | 22 | GB | N | | 9-0 | 23-31-31 | D06016 | 14 | | | SM00104 | | 9 | | 001-099 |
| 2091B | 22 | GB | N | | 9-0 | 23-31-31 | D06016 | 13 | | | SM00103 | | 9 | | 115-199 |
| 2091R | 22 | GB | N | | 0-0 | 23-31-31 | D06016 | 13 | | | SM00103 | | 9 | | 001-099 |
| 2091R | 22 | GB | N | | 0-0 | 23-31-31 | D06016 | 14 | | | SM00104 | | 9 | | 115-199 |
| 2101B | 22 | GB | O | | 12-0 | 23-31-31 | D06018 | 14 | | | SM00104 | | 9 | | 001-099 |
| 2101B | 22 | GB | O | | 12-0 | 23-31-31 | D06018 | 13 | | | SM00103 | | 9 | | 115-199 |
| 2101R | 22 | GB | O | | 0-0 | 23-31-31 | D06018 | 13 | | | SM00103 | | 9 | | 001-099 |
| 2101R | 22 | GB | O | | 0-0 | 23-31-31 | D06018 | 14 | | | SM00104 | | 9 | | 115-199 |
| 2103B | 22 | GB | P | | 7-0 | 23-31-31 | SM00104 | | 9 | | SM00124 | | 9 | | 001-099 |
| 2103B | 22 | GB | P | | 7-0 | 23-31-31 | SM00103 | | 9 | | SM00123 | | 9 | | 115-199 |
| 2103R | 22 | GB | P | | 0-0 | 23-31-31 | SM00103 | | 9 | | SM00123 | | 9 | | 001-099 |
| 2103R | 22 | GB | P | | 0-0 | 23-31-31 | SM00104 | | 9 | | SM00124 | | 9 | | 115-199 |
| 2111B | 22 | GB | Q | | 9-0 | 23-31-31 | D06020 | 14 | | | SM00124 | | 9 | | 001-099 |
| 2111B | 22 | GB | Q | | 9-0 | 23-31-31 | D06020 | 13 | | | SM00123 | | 9 | | 115-199 |
| 2111R | 22 | GB | Q | | 0-0 | 23-31-31 | D06020 | 13 | | | SM00123 | | 9 | | 001-099 |
| 2111R | 22 | GB | Q | | 0-0 | 23-31-31 | D06020 | 14 | | | SM00124 | | 9 | | 115-199 |
| 2121B | 22 | GB | R | | 10-0 | 23-31-31 | D06022 | 14 | | | SM00124 | | 9 | | 001-099 |
| 2121B | 22 | GB | R | | 10-0 | 23-31-31 | D06022 | 13 | | | SM00123 | | 9 | | 115-199 |
| 2121R | 22 | GB | R | | 0-0 | 23-31-31 | D06022 | 13 | | | SM00123 | | 9 | | 001-099 |
| 2121R | 22 | GB | R | | 0-0 | 23-31-31 | D06022 | 14 | | | SM00124 | | 9 | | 115-199 |
| 2123B | 22 | GB | T | | 4-6 | 23-31-31 | SM00124 | | 9 | | SM00144 | | 9 | | 001-099 |
| 2123B | 22 | GB | T | | 4-6 | 23-31-31 | SM00123 | | 9 | | SM00143 | | 9 | | 115-199 |
| 2123R | 22 | GB | T | | 0-0 | 23-31-31 | SM00123 | | 9 | | SM00143 | | 9 | | 001-099 |
| 2123R | 22 | GB | T | | 0-0 | 23-31-31 | SM00124 | | 9 | | SM00144 | | 9 | | 115-199 |
| 2131B | 22 | GB | S | | 10-0 | 23-31-31 | D06024 | 14 | | | SM00144 | | 9 | | 001-099 |
| 2131B | 22 | GB | S | | 10-0 | 23-31-31 | D06024 | 13 | | | SM00143 | | 9 | | 115-199 |
| 2131R | 22 | GB | S | | 0-0 | 23-31-31 | D06024 | 13 | | | SM00143 | | 9 | | 001-099 |
| 2131R | 22 | GB | S | | 0-0 | 23-31-31 | D06024 | 14 | | | SM00144 | | 9 | | 115-199 |
| 2141B | 22 | GB | U | | 11-0 | 23-31-31 | D06026 | 14 | | | SM00144 | | 9 | | 001-099 |
| 2141B | 22 | GB | U | | 11-0 | 23-31-31 | D06026 | 13 | | | SM00143 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 14

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | |
| 2141R | 22 | GB | U | | 0-0 | 23-31-31 | D06026 | | 13 | | SM00143 | | 9 | | 001-099 |
| 2141R | 22 | GB | U | | 0-0 | 23-31-31 | D06026 | | 14 | | SM00144 | | 9 | | 115-199 |
| 2143B | 22 | GB | AP | | 7-0 | 23-31-31 | SM00144 | | | 9 | SM00164 | | 9 | | 001-099 |
| 2143B | 22 | GB | AP | | 7-0 | 23-31-31 | SM00143 | | | 9 | SM00163 | | 9 | | 115-199 |
| 2143R | 22 | GB | AP | | 0-0 | 23-31-31 | SM00143 | | | 9 | SM00163 | | 9 | | 001-099 |
| 2143R | 22 | GB | AP | | 0-0 | 23-31-31 | SM00144 | | | 9 | SM00164 | | 9 | | 115-199 |
| 2151B | 22 | GB | V | | 9-0 | 23-31-31 | D06028 | | 14 | | SM00164 | | 9 | | 001-099 |
| 2151B | 22 | GB | V | | 9-0 | 23-31-31 | D06028 | | 13 | | SM00163 | | 9 | | 115-199 |
| 2151R | 22 | GB | V | | 0-0 | 23-31-31 | D06028 | | 13 | | SM00163 | | 9 | | 001-099 |
| 2151R | 22 | GB | V | | 0-0 | 23-31-31 | D06028 | | 14 | | SM00164 | | 9 | | 115-199 |
| 2161B | 22 | GB | AB | | 9-0 | 23-31-31 | D06030 | | 14 | | SM00164 | | 9 | | 001-099 |
| 2161B | 22 | GB | AB | | 9-0 | 23-31-31 | D06030 | | 13 | | SM00163 | | 9 | | 115-199 |
| 2161R | 22 | GB | AB | | 0-0 | 23-31-31 | D06030 | | 13 | | SM00163 | | 9 | | 001-099 |
| 2161R | 22 | GB | AB | | 0-0 | 23-31-31 | D06030 | | 14 | | SM00164 | | 9 | | 115-199 |
| 2163B | 22 | GB | W | | 8-0 | 23-31-31 | SM00164 | | | 9 | SM00184 | | 9 | | 001-099 |
| 2163B | 22 | GB | W | | 7-0 | 23-31-31 | SM00163 | | | 9 | SM00183 | | 9 | | 115-199 |
| 2163R | 22 | GB | W | | 0-0 | 23-31-31 | SM00163 | | | 9 | SM00183 | | 9 | | 001-099 |
| 2163R | 22 | GB | W | | 0-0 | 23-31-31 | SM00164 | | | 9 | SM00184 | | 9 | | 115-199 |
| 2171B | 22 | GB | Y | | 5-0 | 23-31-31 | D06032 | | 14 | | SM00184 | | 9 | | 001-099 |
| 2171B | 22 | GB | Y | | 4-0 | 23-31-31 | D06032 | | 13 | | SM00183 | | 9 | | 115-199 |
| 2171R | 22 | GB | Y | | 0-0 | 23-31-31 | D06032 | | 13 | | SM00183 | | 9 | | 001-099 |
| 2171R | 22 | GB | Y | | 0-0 | 23-31-31 | D06032 | | 14 | | SM00184 | | 9 | | 115-199 |
| 2181B | 22 | GB | Z | | 5-0 | 23-31-31 | D06034 | | 14 | | SM00184 | | 9 | | 001-099 |
| 2181B | 22 | GB | Z | | 4-0 | 23-31-31 | D06034 | | 13 | | SM00183 | | 9 | | 115-199 |
| 2181R | 22 | GB | Z | | 0-0 | 23-31-31 | D06034 | | 13 | | SM00183 | | 9 | | 001-099 |
| 2181R | 22 | GB | Z | | 0-0 | 23-31-31 | D06034 | | 14 | | SM00184 | | 9 | | 115-199 |
| 2183B | 22 | GB | AA | | 9-0 | 23-31-31 | SM00184 | | | 9 | SM00204 | | 9 | | 001-099 |
| 2183B | 22 | GB | AA | | 9-0 | 23-31-31 | SM00183 | | | 9 | SM00203 | | 9 | | 115-199 |
| 2183R | 22 | GB | AA | | 0-0 | 23-31-31 | SM00183 | | | 9 | SM00203 | | 9 | | 001-099 |
| 2183R | 22 | GB | AA | | 0-0 | 23-31-31 | SM00184 | | | 9 | SM00204 | | 9 | | 115-199 |
| 2191B | 22 | GB | AC | | 8-0 | 23-31-31 | D06036 | | 14 | | SM00204 | | 9 | | 001-099 |
| 2191B | 22 | GB | AC | | 9-0 | 23-31-31 | D06036 | | 13 | | SM00203 | | 9 | | 115-199 |
| 2191R | 22 | GB | AC | | 0-0 | 23-31-31 | D06036 | | 13 | | SM00203 | | 9 | | 001-099 |
| 2191R | 22 | GB | AC | | 0-0 | 23-31-31 | D06036 | | 14 | | SM00204 | | 9 | | 115-199 |
| 2201B | 22 | GB | AE | | 8-0 | 23-31-32 | D06038 | | 14 | | SM00204 | | 9 | | 001-099 |
| 2201B | 22 | GB | AE | | 9-0 | 23-31-32 | D06038 | | 13 | | SM00203 | | 9 | | 115-199 |
| 2201R | 22 | GB | AE | | 0-0 | 23-31-32 | D06038 | | 13 | | SM00203 | | 9 | | 001-099 |
| 2201R | 22 | GB | AE | | 0-0 | 23-31-32 | D06038 | | 14 | | SM00204 | | 9 | | 115-199 |
| 2203B | 22 | GB | AD | | 5-0 | 23-31-32 | SM00204 | | | 9 | SM00244 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 15

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | | To | | | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | | |
| 2203B | 22 | GB | AD | | 6-0 | 23-31-32 | SM00203 | | | 9 | | SM00243 | | 9 | | 115-199 |
| 2203R | 22 | GB | AD | | 0-0 | 23-31-32 | SM00203 | | | 9 | | SM00243 | | 9 | | 001-099 |
| 2203R | 22 | GB | AD | | 0-0 | 23-31-32 | SM00204 | | | 9 | | SM00244 | | 9 | | 115-199 |
| 2211B | 22 | GB | AF | | 9-0 | 23-31-32 | D06040 | | 14 | | | SM00204 | | 9 | | 001-099 |
| 2211B | 22 | GB | AF | | 9-0 | 23-31-32 | D06040 | | 13 | | | SM00203 | | 9 | | 115-199 |
| 2211R | 22 | GB | AF | | 0-0 | 23-31-32 | D06040 | | 13 | | | SM00203 | | 9 | | 001-099 |
| 2211R | 22 | GB | AF | | 0-0 | 23-31-32 | D06040 | | 14 | | | SM00204 | | 9 | | 115-199 |
| 2221B | 22 | GB | AH | | 8-0 | 23-31-32 | D06042 | | 14 | | | SM00244 | | 9 | | 001-099 |
| 2221B | 22 | GB | AH | | 8-0 | 23-31-32 | D06042 | | 13 | | | SM00243 | | 9 | | 115-199 |
| 2221R | 22 | GB | AH | | 0-0 | 23-31-32 | D06042 | | 13 | | | SM00243 | | 9 | | 001-099 |
| 2221R | 22 | GB | AH | | 0-0 | 23-31-32 | D06042 | | 14 | | | SM00244 | | 9 | | 115-199 |
| 2231B | 22 | GB | AI | | 9-0 | 23-31-32 | D06044 | | 14 | | | SM00244 | | 9 | | 001-099 |
| 2231B | 22 | GB | AI | | 9-0 | 23-31-32 | D06044 | | 13 | | | SM00243 | | 9 | | 115-199 |
| 2231R | 22 | GB | AI | | 0-0 | 23-31-32 | D06044 | | 13 | | | SM00243 | | 9 | | 001-099 |
| 2231R | 22 | GB | AI | | 0-0 | 23-31-32 | D06044 | | 14 | | | SM00244 | | 9 | | 115-199 |
| 2241B | 22 | GB | AL | | 8-0 | 23-31-32 | D05872 | | 14 | | | SM00264 | | 9 | | 001-099 |
| 2241B | 22 | GB | AL | | 8-0 | 23-31-32 | D05872 | | 13 | | | SM00263 | | 9 | | 115-199 |
| 2241R | 22 | GB | AL | | 0-0 | 23-31-32 | D05872 | | 13 | | | SM00263 | | 9 | | 001-099 |
| 2241R | 22 | GB | AL | | 0-0 | 23-31-32 | D05872 | | 14 | | | SM00264 | | 9 | | 115-199 |
| 2243B | 22 | GB | AM | | 8-0 | 23-31-32 | SM00244 | | | 9 | | SM00264 | | 9 | | 001-099 |
| 2243B | 22 | GB | AM | | 7-0 | 23-31-32 | SM00243 | | | 9 | | SM00263 | | 9 | | 115-199 |
| 2243R | 22 | GB | AM | | 0-0 | 23-31-32 | SM00243 | | | 9 | | SM00263 | | 9 | | 001-099 |
| 2243R | 22 | GB | AM | | 0-0 | 23-31-32 | SM00244 | | | 9 | | SM00264 | | 9 | | 115-199 |
| 2251B | 22 | GB | AN | | 11-0 | 23-31-32 | D05874 | | 14 | | | SM00264 | | 9 | | 001-099 |
| 2251B | 22 | GB | AN | | 11-0 | 23-31-32 | D05874 | | 13 | | | SM00263 | | 9 | | 115-199 |
| 2251R | 22 | GB | AN | | 0-0 | 23-31-32 | D05874 | | 13 | | | SM00263 | | 9 | | 001-099 |
| 2251R | 22 | GB | AN | | 0-0 | 23-31-32 | D05874 | | 14 | | | SM00264 | | 9 | | 115-199 |
| 2291B | 22 | GB | X | | 9-0 | 23-31-31 | D01241 | | 1 | | | SM00164 | | 9 | | 001-099 |
| 2291B | 22 | GB | X | | 8-0 | 23-31-31 | D01241 | | 1 | | | SM00163 | | 9 | | 115-199 |
| 2291R | 22 | GB | X | | 0-0 | 23-31-31 | D01241 | | 2 | | | SM00163 | | 9 | | 001-099 |
| 2291R | 22 | GB | X | | 0-0 | 23-31-31 | D01241 | | 2 | | | SM00164 | | 9 | | 115-199 |
| 2413B | 22 | GB | A | | 25-0 | 23-31-31 | D40410P | | 13 | | | SM00084 | | 9 | | 001-099 |
| 2413B | 22 | GB | A | | 25-0 | 23-31-31 | D40410P | | 13 | | | SM00083 | | 9 | | 115-199 |
| 2413R | 22 | GB | A | | 0-0 | 23-31-31 | D40410P | | 14 | | | SM00083 | | 9 | | 001-099 |
| 2413R | 22 | GB | A | | 0-0 | 23-31-31 | D40410P | | 14 | | | SM00084 | | 9 | | 115-199 |
| 2423B | 22 | GB | AJ | | 7-0 | 23-31-32 | SM00264 | | | 9 | | D40412J | 14 | | | 001-099 |
| 2423B | 22 | GB | AJ | | 8-0 | 23-31-32 | SM00263 | | | 9 | | D40412J | 13 | | | 115-199 |
| 2423R | 22 | GB | AJ | | 0-0 | 23-31-32 | SM00263 | | | 9 | | D40412J | 13 | | | 001-099 |
| 2423R | 22 | GB | AJ | | 0-0 | 23-31-32 | SM00264 | | | 9 | | D40412J | 14 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 16

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|-------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3802 | 286N3802 | | | | P37TO PSU HARNESS-RIGHT, FORWARD (continued) | | | | | | | | | | | |
| 6019AD | 22 | | GA | | 12-0 | 33-25-21 | | D06000 | | | | 9 | | | | 115-199 |
| 6029AD | 22 | | GA | | 12-0 | 33-25-21 | | D06002 | | | | 9 | | | | 115-199 |
| 6039AD | 22 | | GA | | 8-0 | 33-25-21 | | D06004 | | | | 9 | | | | 115-199 |
| 6049AD | 22 | | GA | | 10-0 | 33-25-21 | | D06006 | | | | 9 | | | | 115-199 |
| 6059AD | 22 | | GA | | 8-0 | 33-25-21 | | D06008 | | | | 9 | | | | 115-199 |
| 6069AD | 22 | | GA | | 11-0 | 33-25-21 | | D06010 | | | | 9 | | | | 115-199 |
| 6079AD | 22 | | GA | | 8-0 | 33-25-21 | | D06012 | | | | 9 | | | | 115-199 |
| 6089AD | 22 | | GA | | 9-0 | 33-25-21 | | D06014 | | | | 9 | | | | 115-199 |
| 6099AD | 22 | | GA | | 9-0 | 33-25-21 | | D06016 | | | | 9 | | | | 115-199 |
| 6109AD | 22 | | GA | | 12-0 | 33-25-21 | | D06018 | | | | 9 | | | | 115-199 |
| 6119AD | 22 | | GA | | 9-0 | 33-25-21 | | D06020 | | | | 9 | | | | 115-199 |
| 6129AD | 22 | | GA | | 10-0 | 33-25-21 | | D06022 | | | | 9 | | | | 115-199 |
| 6139AD | 22 | | GA | | 10-0 | 33-25-21 | | D06024 | | | | 9 | | | | 115-199 |
| 6149AD | 22 | | GA | | 11-0 | 33-25-21 | | D06026 | | | | 9 | | | | 115-199 |
| 6159AD | 22 | | GA | | 9-0 | 33-25-21 | | D06028 | | | | 9 | | | | 115-199 |
| 6169AD | 22 | | GA | | 9-0 | 33-25-21 | | D06030 | | | | 9 | | | | 115-199 |
| 6179AD | 22 | | GA | | 4-0 | 33-25-21 | | D06032 | | | | 9 | | | | 115-199 |
| 6189AD | 22 | | GA | | 4-0 | 33-25-21 | | D06034 | | | | 9 | | | | 115-199 |
| 6199AD | 22 | | GA | | 9-0 | 33-25-22 | | D06036 | | | | 9 | | | | 115-199 |
| 6209AD | 22 | | GA | | 8-0 | 33-25-22 | | D06038 | | | | 9 | | | | 115-199 |
| 6219AD | 22 | | GA | | 9-0 | 33-25-22 | | D06040 | | | | 9 | | | | 115-199 |
| 6229AD | 22 | | GA | | 8-0 | 33-25-22 | | D06042 | | | | 9 | | | | 115-199 |
| 6239AD | 22 | | GA | | 12-0 | 33-25-22 | | D06044 | | | | 9 | | | | 115-199 |
| 6249AD | 22 | | GA | | 8-0 | 33-25-22 | | D05872 | | | | 9 | | | | 115-199 |
| 6259AD | 22 | | GA | | 11-0 | 33-25-22 | | D05874 | | | | 9 | | | | 115-199 |
| 6519AD | 22 | | GA | | 4-0 | 33-25-21 | | SM06019 | | | 9 | | | | | 115-199 |
| 6539AD | 22 | | GA | | 5-0 | 33-25-21 | | SM06039 | | | 9 | | | | | 115-199 |
| 6559AD | 22 | | GA | | 5-0 | 33-25-21 | | SM06059 | | | 9 | | | | | 115-199 |
| 6579AD | 22 | | GA | | 3-0 | 33-25-21 | | SM06079 | | | 9 | | | | | 115-199 |
| 6599AD | 22 | | GA | | 7-0 | 33-25-21 | | SM06099 | | | 9 | | | | | 115-199 |
| 6619AD | 22 | | GA | | 4-0 | 33-25-21 | | SM06119 | | | 9 | | | | | 115-199 |
| 6639AD | 22 | | GA | | 7-0 | 33-25-21 | | SM06139 | | | 9 | | | | | 115-199 |
| 6659AD | 22 | | GA | | 7-0 | 33-25-21 | | SM06159 | | | 9 | | | | | 115-199 |
| 6679AD | 22 | | GA | | 5-0 | 33-25-21 | | SM06179 | | | 9 | | | | | 115-199 |
| 6699AD | 22 | | GA | | 5-0 | 33-25-22 | | SM06199 | | | 9 | | | | | 115-199 |
| 6739AD | 22 | | GA | | 7-0 | 33-25-22 | | SM06239 | | | 9 | | | | | 115-199 |
| W3804 | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER | | | | | | | | | | | |
| 0011G | 16 | | GA | | 9-6 | 33-24-22 | | D06046 | | | | 1 | | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 17

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | |
| 0011G | 16 | | GA | | 8-0 | 33-24-22 | D06046 | | | | SM00011 | | | 9 | 115-199 |
| 0012WV | 22 | | GA | | 9-6 | 33-25-22 | D06046 | | | | SM00012 | | | 9 | 001-099 |
| 0012WV | 22 | | GA | | 8-0 | 33-25-22 | D06046 | | | | SM00012 | | | 9 | 115-199 |
| 0013WG | 22 | | GA | | 9-6 | 33-25-22 | D06046 | | | | SM00013 | | | 9 | 001-099 |
| 0013WG | 22 | | GA | | 8-0 | 33-25-22 | D06046 | | | | SM00013 | | | 9 | 115-199 |
| 0014WO | 22 | | GA | | 9-6 | 33-25-22 | D06046 | | | | SM00014 | | | 9 | 001-099 |
| 0014WO | 22 | | GA | | 8-0 | 33-25-22 | D06046 | | | | SM00014 | | | 9 | 115-199 |
| 0015V | 22 | | GA | | 9-6 | 33-25-22 | D06046 | | | | SM00015 | | | 9 | 001-099 |
| 0015V | 22 | | GA | | 8-0 | 33-25-22 | D06046 | | | | SM00015 | | | 9 | 115-199 |
| 0016WN | 16 | | GA | | 9-6 | 33-23-22 | D06046 | | | | SM00016 | | | 9 | 001-099 |
| 0016WN | 16 | | GA | | 8-0 | 33-23-22 | D06046 | | | | SM00016 | | | 9 | 115-199 |
| 0017W | 20 | | GA | | 9-6 | 33-24-22 | D06046 | | | | SM00017 | | | 9 | 001-099 |
| 0017W | 20 | | GA | | 8-0 | 33-24-22 | D06046 | | | | SM00017 | | | 9 | 115-199 |
| 0018WP | 16 | | GA | | 9-6 | 33-23-22 | D06046 | | | | SM00018 | | | 9 | 001-099 |
| 0018WP | 16 | | GA | | 8-0 | 33-23-22 | D06046 | | | | SM00018 | | | 9 | 115-199 |
| 0019AJ | 20 | | GA | | 9-6 | 35-21-21 | D06046 | | | 11 | SM00019 | | | 9 | 001-099 |
| 0019AJ | 20 | | GA | | 8-0 | 35-21-21 | D06046 | | | 11 | SM00019 | | | 9 | 115-199 |
| 0020K | 18 | | GA | | 9-6 | 35-21-21 | D06046 | | | 10 | SM00020 | | | 9 | 001-099 |
| 0020K | 18 | | GA | | 8-0 | 35-21-21 | D06046 | | | 10 | SM00020 | | | 9 | 115-199 |
| 0021G | 16 | | GA | | 8-5 | 33-24-22 | D06048 | | | 1 | SM00011 | | | 9 | 001-099 |
| 0021G | 16 | | GA | | 8-0 | 33-24-22 | D06048 | | | 1 | SM00011 | | | 9 | 115-199 |
| 0022WV | 22 | | GA | | 8-5 | 33-25-22 | D06048 | | | 2 | SM00012 | | | 9 | 001-099 |
| 0022WV | 22 | | GA | | 8-0 | 33-25-22 | D06048 | | | 2 | SM00012 | | | 9 | 115-199 |
| 0023WG | 22 | | GA | | 8-5 | 33-25-22 | D06048 | | | 3 | SM00013 | | | 9 | 001-099 |
| 0023WG | 22 | | GA | | 8-0 | 33-25-22 | D06048 | | | 3 | SM00013 | | | 9 | 115-199 |
| 0024WO | 22 | | GA | | 8-5 | 33-25-22 | D06048 | | | 4 | SM00014 | | | 9 | 001-099 |
| 0024WO | 22 | | GA | | 8-0 | 33-25-22 | D06048 | | | 4 | SM00014 | | | 9 | 115-199 |
| 0025V | 22 | | GA | | 8-5 | 33-25-22 | D06048 | | | 5 | SM00015 | | | 9 | 001-099 |
| 0025V | 22 | | GA | | 8-0 | 33-25-22 | D06048 | | | 5 | SM00015 | | | 9 | 115-199 |
| 0026WN | 16 | | GA | | 8-5 | 33-23-22 | D06048 | | | 6 | SM00016 | | | 9 | 001-099 |
| 0026WN | 16 | | GA | | 8-0 | 33-23-22 | D06048 | | | 6 | SM00016 | | | 9 | 115-199 |
| 0027W | 20 | | GA | | 8-5 | 33-24-22 | D06048 | | | 7 | SM00017 | | | 9 | 001-099 |
| 0027W | 20 | | GA | | 8-0 | 33-24-22 | D06048 | | | 7 | SM00017 | | | 9 | 115-199 |
| 0028WP | 16 | | GA | | 8-5 | 33-23-22 | D06048 | | | 8 | SM00018 | | | 9 | 001-099 |
| 0028WP | 16 | | GA | | 8-0 | 33-23-22 | D06048 | | | 8 | SM00018 | | | 9 | 115-199 |
| 0029AJ | 20 | | GA | | 8-5 | 35-21-21 | D06048 | | | 11 | SM00019 | | | 9 | 001-099 |
| 0029AJ | 20 | | GA | | 8-0 | 35-21-21 | D06048 | | | 11 | SM00019 | | | 9 | 115-199 |
| 0030K | 18 | | GA | | 8-5 | 35-21-21 | D06048 | | | 10 | SM00020 | | | 9 | 001-099 |
| 0030K | 18 | | GA | | 8-0 | 35-21-21 | D06048 | | | 10 | SM00020 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 18

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | | | |
| 0031G | 16 | | GA | | 8-0 | 33-24-22 | | D06050 | | | | SM00031 | | 9 | | 001-099 |
| 0031G | 16 | | GA | | 9-0 | 33-24-22 | | D06050 | | | | SM00031 | | 9 | | 115-199 |
| 0032WV | 22 | | GA | | 8-0 | 33-25-22 | | D06050 | | | | SM00032 | | 9 | | 001-099 |
| 0032WV | 22 | | GA | | 9-0 | 33-25-22 | | D06050 | | | | SM00032 | | 9 | | 115-199 |
| 0033WG | 22 | | GA | | 8-0 | 33-25-22 | | D06050 | | | | SM00033 | | 9 | | 001-099 |
| 0033WG | 22 | | GA | | 9-0 | 33-25-22 | | D06050 | | | | SM00033 | | 9 | | 115-199 |
| 0034WO | 22 | | GA | | 8-0 | 33-25-22 | | D06050 | | | | SM00034 | | 9 | | 001-099 |
| 0034WO | 22 | | GA | | 9-0 | 33-25-22 | | D06050 | | | | SM00034 | | 9 | | 115-199 |
| 0035V | 22 | | GA | | 8-0 | 33-25-22 | | D06050 | | | | SM00035 | | 9 | | 001-099 |
| 0035V | 22 | | GA | | 9-0 | 33-25-22 | | D06050 | | | | SM00035 | | 9 | | 115-199 |
| 0036WN | 16 | | GA | | 8-0 | 33-23-22 | | D06050 | | | | SM00036 | | 9 | | 001-099 |
| 0036WN | 16 | | GA | | 9-0 | 33-23-22 | | D06050 | | | | SM00036 | | 9 | | 115-199 |
| 0037W | 20 | | GA | | 8-0 | 33-24-22 | | D06050 | | | | SM00037 | | 9 | | 001-099 |
| 0037W | 20 | | GA | | 9-0 | 33-24-22 | | D06050 | | | | SM00037 | | 9 | | 115-199 |
| 0038WP | 16 | | GA | | 8-0 | 33-23-22 | | D06050 | | | | SM00038 | | 9 | | 001-099 |
| 0038WP | 16 | | GA | | 9-0 | 33-23-22 | | D06050 | | | | SM00038 | | 9 | | 115-199 |
| 0039AJ | 20 | | GA | | 8-0 | 35-21-21 | | D06050 | | | | SM00039 | | 9 | | 001-099 |
| 0039AJ | 20 | | GA | | 9-0 | 35-21-21 | | D06050 | | | | SM00039 | | 9 | | 115-199 |
| 0040K | 18 | | GA | | 8-0 | 35-21-21 | | D06050 | | | | SM00040 | | 9 | | 001-099 |
| 0040K | 18 | | GA | | 9-0 | 35-21-21 | | D06050 | | | | SM00040 | | 9 | | 115-199 |
| 0041G | 16 | | GA | | 10-11 | 33-24-22 | | D06052 | | | | SM00031 | | 9 | | 001-099 |
| 0041G | 16 | | GA | | 13-0 | 33-24-22 | | D06052 | | | | SM00031 | | 9 | | 115-199 |
| 0042WV | 22 | | GA | | 10-11 | 33-25-22 | | D06052 | | | | SM00032 | | 9 | | 001-099 |
| 0042WV | 22 | | GA | | 13-0 | 33-25-22 | | D06052 | | | | SM00032 | | 9 | | 115-199 |
| 0043WG | 22 | | GA | | 10-11 | 33-25-22 | | D06052 | | | | SM00033 | | 9 | | 001-099 |
| 0043WG | 22 | | GA | | 13-0 | 33-25-22 | | D06052 | | | | SM00033 | | 9 | | 115-199 |
| 0044WO | 22 | | GA | | 10-11 | 33-25-22 | | D06052 | | | | SM00034 | | 9 | | 001-099 |
| 0044WO | 22 | | GA | | 13-0 | 33-25-22 | | D06052 | | | | SM00034 | | 9 | | 115-199 |
| 0045V | 22 | | GA | | 10-11 | 33-25-22 | | D06052 | | | | SM00035 | | 9 | | 001-099 |
| 0045V | 22 | | GA | | 13-0 | 33-25-22 | | D06052 | | | | SM00035 | | 9 | | 115-199 |
| 0046WN | 16 | | GA | | 10-11 | 33-23-22 | | D06052 | | | | SM00036 | | 9 | | 001-099 |
| 0046WN | 16 | | GA | | 13-0 | 33-23-22 | | D06052 | | | | SM00036 | | 9 | | 115-199 |
| 0047W | 20 | | GA | | 10-11 | 33-24-22 | | D06052 | | | | SM00037 | | 9 | | 001-099 |
| 0047W | 20 | | GA | | 13-0 | 33-24-22 | | D06052 | | | | SM00037 | | 9 | | 115-199 |
| 0048WP | 16 | | GA | | 10-11 | 33-23-22 | | D06052 | | | | SM00038 | | 9 | | 001-099 |
| 0048WP | 16 | | GA | | 13-0 | 33-23-22 | | D06052 | | | | SM00038 | | 9 | | 115-199 |
| 0049AJ | 20 | | GA | | 10-11 | 35-21-21 | | D06052 | | | | SM00039 | | 9 | | 001-099 |
| 0049AJ | 20 | | GA | | 13-0 | 35-21-21 | | D06052 | | | | SM00039 | | 9 | | 115-199 |
| 0050K | 18 | | GA | | 10-11 | 35-21-21 | | D06052 | | | | SM00040 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 19

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | |
| 0050K | 18 | | GA | | 13-0 | 35-21-21 | D06052 | | 10 | | SM00040 | | 9 | | 115-199 |
| 0051G | 16 | | GA | | 8-11 | 33-24-22 | D06054 | | 1 | | SM00051 | | 9 | | 001-099 |
| 0051G | 16 | | GA | | 11-0 | 33-24-22 | D06054 | | 1 | | SM00051 | | 9 | | 115-199 |
| 0052WV | 22 | | GA | | 8-11 | 33-25-23 | D06054 | | 2 | | SM00052 | | 9 | | 001-099 |
| 0052WV | 22 | | GA | | 11-0 | 33-25-23 | D06054 | | 2 | | SM00052 | | 9 | | 115-199 |
| 0053WG | 22 | | GA | | 8-11 | 33-25-23 | D06054 | | 3 | | SM00053 | | 9 | | 001-099 |
| 0053WG | 22 | | GA | | 11-0 | 33-25-23 | D06054 | | 3 | | SM00053 | | 9 | | 115-199 |
| 0055V | 22 | | GA | | 8-11 | 33-25-23 | D06054 | | 5 | | SM00055 | | 9 | | 001-099 |
| 0055V | 22 | | GA | | 11-0 | 33-25-23 | D06054 | | 5 | | SM00055 | | 9 | | 115-199 |
| 0056WN | 16 | | GA | | 8-11 | 33-23-23 | D06054 | | 6 | | SM00056 | | 9 | | 001-099 |
| 0056WN | 16 | | GA | | 11-0 | 33-23-23 | D06054 | | 6 | | SM00056 | | 9 | | 115-199 |
| 0057W | 20 | | GA | | 8-11 | 33-24-22 | D06054 | | 7 | | SM00057 | | 9 | | 001-099 |
| 0057W | 20 | | GA | | 11-0 | 33-24-22 | D06054 | | 7 | | SM00057 | | 9 | | 115-199 |
| 0058WP | 16 | | GA | | 8-11 | 33-23-23 | D06054 | | 8 | | SM00058 | | 9 | | 001-099 |
| 0058WP | 16 | | GA | | 11-0 | 33-23-23 | D06054 | | 8 | | SM00058 | | 9 | | 115-199 |
| 0059AJ | 20 | | GA | | 8-11 | 35-21-22 | D06054 | | 11 | | SM00059 | | 9 | | 001-099 |
| 0059AJ | 20 | | GA | | 11-0 | 35-21-22 | D06054 | | 11 | | SM00059 | | 9 | | 115-199 |
| 0060K | 18 | | GA | | 8-11 | 35-21-22 | D06054 | | 10 | | SM00060 | | 9 | | 001-099 |
| 0060K | 18 | | GA | | 11-0 | 35-21-22 | D06054 | | 10 | | SM00060 | | 9 | | 115-199 |
| 0061G | 16 | | GA | | 9-4 | 33-24-22 | D06056 | | 1 | | SM00051 | | 9 | | 001-099 |
| 0061G | 16 | | GA | | 12-0 | 33-24-22 | D06056 | | 1 | | SM00051 | | 9 | | 115-199 |
| 0062WV | 22 | | GA | | 9-4 | 33-25-23 | D06056 | | 2 | | SM00052 | | 9 | | 001-099 |
| 0062WV | 22 | | GA | | 12-0 | 33-25-23 | D06056 | | 2 | | SM00052 | | 9 | | 115-199 |
| 0063WG | 22 | | GA | | 9-4 | 33-25-23 | D06056 | | 3 | | SM00053 | | 9 | | 001-099 |
| 0063WG | 22 | | GA | | 12-0 | 33-25-23 | D06056 | | 3 | | SM00053 | | 9 | | 115-199 |
| 0065V | 22 | | GA | | 9-4 | 33-25-23 | D06056 | | 5 | | SM00055 | | 9 | | 001-099 |
| 0065V | 22 | | GA | | 12-0 | 33-25-23 | D06056 | | 5 | | SM00055 | | 9 | | 115-199 |
| 0066WN | 16 | | GA | | 9-4 | 33-23-23 | D06056 | | 6 | | SM00056 | | 9 | | 001-099 |
| 0066WN | 16 | | GA | | 12-0 | 33-23-23 | D06056 | | 6 | | SM00056 | | 9 | | 115-199 |
| 0067W | 20 | | GA | | 9-4 | 33-24-22 | D06056 | | 7 | | SM00057 | | 9 | | 001-099 |
| 0067W | 20 | | GA | | 12-0 | 33-24-22 | D06056 | | 7 | | SM00057 | | 9 | | 115-199 |
| 0068WP | 16 | | GA | | 9-4 | 33-23-23 | D06056 | | 8 | | SM00058 | | 9 | | 001-099 |
| 0068WP | 16 | | GA | | 12-0 | 33-23-23 | D06056 | | 8 | | SM00058 | | 9 | | 115-199 |
| 0069AJ | 20 | | GA | | 9-4 | 35-21-22 | D06056 | | 11 | | SM00059 | | 9 | | 001-099 |
| 0069AJ | 20 | | GA | | 12-0 | 35-21-22 | D06056 | | 11 | | SM00059 | | 9 | | 115-199 |
| 0070K | 18 | | GA | | 9-4 | 35-21-22 | D06056 | | 10 | | SM00060 | | 9 | | 001-099 |
| 0070K | 18 | | GA | | 12-0 | 35-21-22 | D06056 | | 10 | | SM00060 | | 9 | | 115-199 |
| 0071G | 16 | | GA | | 9-11 | 33-24-22 | D06058 | | 1 | | SM00071 | | 9 | | 001-099 |
| 0071G | 16 | | GA | | 9-0 | 33-24-22 | D06058 | | 1 | | SM00071 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 20

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|---------------------------------------|----------|--------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3804 | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | | | |
| 0072WV | 22 | | GA | | 9-11 | 33-25-23 | D06058 | | 2 | | SM00072 | | 9 | | 001-099 | |
| 0072WV | 22 | | GA | | 9-0 | 33-25-23 | D06058 | | 2 | | SM00072 | | 9 | | 115-199 | |
| 0073WG | 22 | | GA | | 9-11 | 33-25-23 | D06058 | | 3 | | SM00073 | | 9 | | 001-099 | |
| 0073WG | 22 | | GA | | 9-0 | 33-25-23 | D06058 | | 3 | | SM00073 | | 9 | | 115-199 | |
| 0075V | 22 | | GA | | 9-11 | 33-25-23 | D06058 | | 5 | | SM00075 | | 9 | | 001-099 | |
| 0075V | 22 | | GA | | 9-0 | 33-25-23 | D06058 | | 5 | | SM00075 | | 9 | | 115-199 | |
| 0076WN | 16 | | GA | | 9-11 | 33-23-23 | D06058 | | 6 | | SM00076 | | 9 | | 001-099 | |
| 0076WN | 16 | | GA | | 9-0 | 33-23-23 | D06058 | | 6 | | SM00076 | | 9 | | 115-199 | |
| 0077W | 20 | | GA | | 9-11 | 33-24-22 | D06058 | | 7 | | SM00077 | | 9 | | 001-099 | |
| 0077W | 20 | | GA | | 9-0 | 33-24-22 | D06058 | | 7 | | SM00077 | | 9 | | 115-199 | |
| 0078WP | 16 | | GA | | 9-11 | 33-23-23 | D06058 | | 8 | | SM00078 | | 9 | | 001-099 | |
| 0078WP | 16 | | GA | | 9-0 | 33-23-23 | D06058 | | 8 | | SM00078 | | 9 | | 115-199 | |
| 0079AJ | 20 | | GA | | 9-11 | 35-21-22 | D06058 | | 11 | | SM00079 | | 9 | | 001-099 | |
| 0079AJ | 20 | | GA | | 9-0 | 35-21-22 | D06058 | | 11 | | SM00079 | | 9 | | 115-199 | |
| 0080K | 18 | | GA | | 9-11 | 35-21-22 | D06058 | | 10 | | SM00080 | | 9 | | 001-099 | |
| 0080K | 18 | | GA | | 9-0 | 35-21-22 | D06058 | | 10 | | SM00080 | | 9 | | 115-199 | |
| 0081G | 16 | | GA | | 11-10 | 33-24-22 | D06060 | | 1 | | SM00071 | | 9 | | 001-099 | |
| 0081G | 16 | | GA | | 11-0 | 33-24-22 | D06060 | | 1 | | SM00071 | | 9 | | 115-199 | |
| 0082WV | 22 | | GA | | 11-10 | 33-25-23 | D06060 | | 2 | | SM00072 | | 9 | | 001-099 | |
| 0082WV | 22 | | GA | | 11-0 | 33-25-23 | D06060 | | 2 | | SM00072 | | 9 | | 115-199 | |
| 0083WG | 22 | | GA | | 11-10 | 33-25-23 | D06060 | | 3 | | SM00073 | | 9 | | 001-099 | |
| 0083WG | 22 | | GA | | 11-0 | 33-25-23 | D06060 | | 3 | | SM00073 | | 9 | | 115-199 | |
| 0085V | 22 | | GA | | 11-10 | 33-25-23 | D06060 | | 5 | | SM00075 | | 9 | | 001-099 | |
| 0085V | 22 | | GA | | 11-0 | 33-25-23 | D06060 | | 5 | | SM00075 | | 9 | | 115-199 | |
| 0086WN | 16 | | GA | | 11-10 | 33-23-23 | D06060 | | 6 | | SM00076 | | 9 | | 001-099 | |
| 0086WN | 16 | | GA | | 11-0 | 33-23-23 | D06060 | | 6 | | SM00076 | | 9 | | 115-199 | |
| 0087W | 20 | | GA | | 11-10 | 33-24-22 | D06060 | | 7 | | SM00077 | | 9 | | 001-099 | |
| 0087W | 20 | | GA | | 11-0 | 33-24-22 | D06060 | | 7 | | SM00077 | | 9 | | 115-199 | |
| 0088WP | 16 | | GA | | 11-10 | 33-23-23 | D06060 | | 8 | | SM00078 | | 9 | | 001-099 | |
| 0088WP | 16 | | GA | | 11-0 | 33-23-23 | D06060 | | 8 | | SM00078 | | 9 | | 115-199 | |
| 0089AJ | 20 | | GA | | 11-10 | 35-21-22 | D06060 | | 11 | | SM00079 | | 9 | | 001-099 | |
| 0089AJ | 20 | | GA | | 11-0 | 35-21-22 | D06060 | | 11 | | SM00079 | | 9 | | 115-199 | |
| 0090K | 18 | | GA | | 11-10 | 35-21-22 | D06060 | | 10 | | SM00080 | | 9 | | 001-099 | |
| 0090K | 18 | | GA | | 11-0 | 35-21-22 | D06060 | | 10 | | SM00080 | | 9 | | 115-199 | |
| 0091G | 16 | | GA | | 8-9 | 33-24-22 | D06062 | | 1 | | SM00091 | | 9 | | 001-099 | |
| 0091G | 16 | | GA | | 8-0 | 33-24-22 | D06062 | | 1 | | SM00091 | | 9 | | 115-199 | |
| 0092WV | 22 | | GA | | 8-9 | 33-25-23 | D06062 | | 2 | | SM00092 | | 9 | | 001-099 | |
| 0092WV | 22 | | GA | | 8-0 | 33-25-23 | D06062 | | 2 | | SM00092 | | 9 | | 115-199 | |
| 0093WG | 22 | | GA | | 8-9 | 33-25-23 | D06062 | | 3 | | SM00093 | | 9 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 21

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | |
| 0093WG | 22 | GA | | | 8-0 | 33-25-23 | D06062 | | | 3 | SM00093 | | | 9 | 115-199 |
| 0095V | 22 | GA | | | 8-9 | 33-25-23 | D06062 | | | 5 | SM00095 | | | 9 | 001-099 |
| 0095V | 22 | GA | | | 8-0 | 33-25-23 | D06062 | | | 5 | SM00095 | | | 9 | 115-199 |
| 0096WN | 16 | GA | | | 8-9 | 33-23-23 | D06062 | | | 6 | SM00096 | | | 9 | 001-099 |
| 0096WN | 16 | GA | | | 8-0 | 33-23-23 | D06062 | | | 6 | SM00096 | | | 9 | 115-199 |
| 0097W | 20 | GA | | | 8-9 | 33-24-22 | D06062 | | | 7 | SM00097 | | | 9 | 001-099 |
| 0097W | 20 | GA | | | 8-0 | 33-24-22 | D06062 | | | 7 | SM00097 | | | 9 | 115-199 |
| 0098WP | 16 | GA | | | 8-9 | 33-23-23 | D06062 | | | 8 | SM00098 | | | 9 | 001-099 |
| 0098WP | 16 | GA | | | 8-0 | 33-23-23 | D06062 | | | 8 | SM00098 | | | 9 | 115-199 |
| 0099AJ | 20 | GA | | | 8-9 | 35-21-22 | D06062 | | | 11 | SM00099 | | | 9 | 001-099 |
| 0099AJ | 20 | GA | | | 8-0 | 35-21-22 | D06062 | | | 11 | SM00099 | | | 9 | 115-199 |
| 0100K | 18 | GA | | | 8-9 | 35-21-22 | D06062 | | | 10 | SM00100 | | | 9 | 001-099 |
| 0100K | 18 | GA | | | 8-0 | 35-21-22 | D06062 | | | 10 | SM00100 | | | 9 | 115-199 |
| 0101G | 16 | GA | | | 10-3 | 33-24-22 | D06064 | | | 1 | SM00091 | | | 9 | 001-099 |
| 0101G | 16 | GA | | | 10-0 | 33-24-22 | D06064 | | | 1 | SM00091 | | | 9 | 115-199 |
| 0102WV | 22 | GA | | | 10-3 | 33-25-23 | D06064 | | | 2 | SM00092 | | | 9 | 001-099 |
| 0102WV | 22 | GA | | | 10-0 | 33-25-23 | D06064 | | | 2 | SM00092 | | | 9 | 115-199 |
| 0103WG | 22 | GA | | | 10-3 | 33-25-23 | D06064 | | | 3 | SM00093 | | | 9 | 001-099 |
| 0103WG | 22 | GA | | | 10-0 | 33-25-23 | D06064 | | | 3 | SM00093 | | | 9 | 115-199 |
| 0105V | 22 | GA | | | 10-3 | 33-25-23 | D06064 | | | 5 | SM00095 | | | 9 | 001-099 |
| 0105V | 22 | GA | | | 10-0 | 33-25-23 | D06064 | | | 5 | SM00095 | | | 9 | 115-199 |
| 0106WN | 16 | GA | | | 10-3 | 33-23-23 | D06064 | | | 6 | SM00096 | | | 9 | 001-099 |
| 0106WN | 16 | GA | | | 10-0 | 33-23-23 | D06064 | | | 6 | SM00096 | | | 9 | 115-199 |
| 0107W | 20 | GA | | | 10-3 | 33-24-22 | D06064 | | | 7 | SM00097 | | | 9 | 001-099 |
| 0107W | 20 | GA | | | 10-0 | 33-24-22 | D06064 | | | 7 | SM00097 | | | 9 | 115-199 |
| 0108WP | 16 | GA | | | 10-3 | 33-23-23 | D06064 | | | 8 | SM00098 | | | 9 | 001-099 |
| 0108WP | 16 | GA | | | 10-0 | 33-23-23 | D06064 | | | 8 | SM00098 | | | 9 | 115-199 |
| 0109AJ | 20 | GA | | | 10-3 | 35-21-22 | D06064 | | | 11 | SM00099 | | | 9 | 001-099 |
| 0109AJ | 20 | GA | | | 10-0 | 35-21-22 | D06064 | | | 11 | SM00099 | | | 9 | 115-199 |
| 0110K | 18 | GA | | | 10-3 | 35-21-22 | D06064 | | | 10 | SM00100 | | | 9 | 001-099 |
| 0110K | 18 | GA | | | 10-0 | 35-21-22 | D06064 | | | 10 | SM00100 | | | 9 | 115-199 |
| 0111G | 16 | GA | | | 8-4 | 33-24-22 | D06066 | | | 1 | SM00111 | | | 9 | 001-099 |
| 0111G | 16 | GA | | | 8-0 | 33-24-22 | D06066 | | | 1 | SM00111 | | | 9 | 115-199 |
| 0112WV | 22 | GA | | | 8-4 | 33-25-23 | D06066 | | | 2 | SM00112 | | | 9 | 001-099 |
| 0112WV | 22 | GA | | | 8-0 | 33-25-23 | D06066 | | | 2 | SM00112 | | | 9 | 115-199 |
| 0113WG | 22 | GA | | | 8-4 | 33-25-23 | D06066 | | | 3 | SM00113 | | | 9 | 001-099 |
| 0113WG | 22 | GA | | | 8-0 | 33-25-23 | D06066 | | | 3 | SM00113 | | | 9 | 115-199 |
| 0115V | 22 | GA | | | 8-4 | 33-25-23 | D06066 | | | 5 | SM00115 | | | 9 | 001-099 |
| 0115V | 22 | GA | | | 8-0 | 33-25-23 | D06066 | | | 5 | SM00115 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 22

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | | | |
| 0116WN | 16 | | GA | | 8-4 | 33-23-23 | | D06066 | | 6 | | SM00116 | | 9 | | 001-099 |
| 0116WN | 16 | | GA | | 8-0 | 33-23-23 | | D06066 | | 6 | | SM00116 | | 9 | | 115-199 |
| 0117W | 20 | | GA | | 8-4 | 33-24-22 | | D06066 | | 7 | | SM00117 | | 9 | | 001-099 |
| 0117W | 20 | | GA | | 8-0 | 33-24-22 | | D06066 | | 7 | | SM00117 | | 9 | | 115-199 |
| 0118WP | 16 | | GA | | 8-4 | 33-23-23 | | D06066 | | 8 | | SM00118 | | 9 | | 001-099 |
| 0118WP | 16 | | GA | | 8-0 | 33-23-23 | | D06066 | | 8 | | SM00118 | | 9 | | 115-199 |
| 0119AJ | 20 | | GA | | 8-4 | 35-21-22 | | D06066 | | 11 | | SM00119 | | 9 | | 001-099 |
| 0119AJ | 20 | | GA | | 8-0 | 35-21-22 | | D06066 | | 11 | | SM00119 | | 9 | | 115-199 |
| 0120K | 18 | | GA | | 8-4 | 35-21-22 | | D06066 | | 10 | | SM00120 | | 9 | | 001-099 |
| 0120K | 18 | | GA | | 8-0 | 35-21-22 | | D06066 | | 10 | | SM00120 | | 9 | | 115-199 |
| 0411G | 16 | | GA | | 4-3 | 33-24-22 | | SM00011 | | | 9 | SM00031 | | 9 | | 001-099 |
| 0411G | 16 | | GA | | 4-0 | 33-24-22 | | SM00011 | | | 9 | SM00031 | | 9 | | 115-199 |
| 0412WV | 22 | | GA | | 4-3 | 33-25-22 | | SM00012 | | | 9 | SM00032 | | 9 | | 001-099 |
| 0412WV | 22 | | GA | | 4-0 | 33-25-22 | | SM00012 | | | 9 | SM00032 | | 9 | | 115-199 |
| 0413WG | 22 | | GA | | 4-3 | 33-25-22 | | SM00013 | | | 9 | SM00033 | | 9 | | 001-099 |
| 0413WG | 22 | | GA | | 4-0 | 33-25-22 | | SM00013 | | | 9 | SM00033 | | 9 | | 115-199 |
| 0414WO | 22 | | GA | | 4-3 | 33-25-22 | | SM00014 | | | 9 | SM00034 | | 9 | | 001-099 |
| 0414WO | 22 | | GA | | 4-0 | 33-25-22 | | SM00014 | | | 9 | SM00034 | | 9 | | 115-199 |
| 0415V | 22 | | GA | | 4-3 | 33-25-22 | | SM00015 | | | 9 | SM00035 | | 9 | | 001-099 |
| 0415V | 22 | | GA | | 4-0 | 33-25-22 | | SM00015 | | | 9 | SM00035 | | 9 | | 115-199 |
| 0416WN | 16 | | GA | | 4-3 | 33-23-22 | | SM00016 | | | 9 | SM00036 | | 9 | | 001-099 |
| 0416WN | 16 | | GA | | 4-0 | 33-23-22 | | SM00016 | | | 9 | SM00036 | | 9 | | 115-199 |
| 0417W | 20 | | GA | | 4-3 | 33-24-22 | | SM00017 | | | 9 | SM00037 | | 9 | | 001-099 |
| 0417W | 20 | | GA | | 4-0 | 33-24-22 | | SM00017 | | | 9 | SM00037 | | 9 | | 115-199 |
| 0418WP | 16 | | GA | | 4-3 | 33-23-22 | | SM00018 | | | 9 | SM00038 | | 9 | | 001-099 |
| 0418WP | 16 | | GA | | 4-0 | 33-23-22 | | SM00018 | | | 9 | SM00038 | | 9 | | 115-199 |
| 0419AJ | 16 | | GA | | 4-3 | 35-21-21 | | SM00019 | | | 9 | SM00039 | | 9 | | 001-099 |
| 0419AJ | 16 | | GA | | 4-0 | 35-21-21 | | SM00019 | | | 9 | SM00039 | | 9 | | 115-199 |
| 0420K | 18 | | GA | | 4-3 | 35-21-21 | | SM00020 | | | 9 | SM00040 | | 9 | | 001-099 |
| 0420K | 18 | | GA | | 4-0 | 35-21-21 | | SM00020 | | | 9 | SM00040 | | 9 | | 115-199 |
| 0431G | 16 | | GA | | 6-6 | 33-24-22 | | SM00031 | | | 9 | SM00051 | | 9 | | 001-099 |
| 0431G | 16 | | GA | | 5-0 | 33-24-22 | | SM00031 | | | 9 | SM00051 | | 9 | | 115-199 |
| 0432WV | 22 | | GA | | 6-6 | 33-25-22 | | SM00032 | | | 9 | SM00052 | | 9 | | 001-099 |
| 0432WV | 22 | | GA | | 5-0 | 33-25-22 | | SM00032 | | | 9 | SM00052 | | 9 | | 115-199 |
| 0433WG | 22 | | GA | | 5-0 | 33-25-22 | | SM00033 | | | 9 | SM00053 | | 9 | | 115-199 |
| 0437W | 20 | | GA | | 6-6 | 33-24-22 | | SM00037 | | | 9 | SM00057 | | 9 | | 001-099 |
| 0437W | 20 | | GA | | 5-0 | 33-24-22 | | SM00037 | | | 9 | SM00057 | | 9 | | 115-199 |
| 0438WP | 16 | | GA | | 6-6 | 33-23-22 | | SM00038 | | | 9 | SM00058 | | 9 | | 001-099 |
| 0438WP | 16 | | GA | | 5-0 | 33-23-22 | | SM00038 | | | 9 | SM00058 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 23

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | |
| 0440K | 18 | | GA | | 6-6 | 35-21-22 | SM00040 | | | 9 | SM00060 | | | 9 | 001-099 |
| 0440K | 18 | | GA | | 5-0 | 35-21-22 | SM00040 | | | 9 | SM00060 | | | 9 | 115-199 |
| 0451G | 16 | | GA | | 7-11 | 33-24-22 | SM00051 | | | 9 | SM00071 | | | 9 | 001-099 |
| 0451G | 16 | | GA | | 9-0 | 33-24-22 | SM00051 | | | 9 | SM00071 | | | 9 | 115-199 |
| 0452WV | 22 | | GA | | 7-11 | 33-25-23 | SM00052 | | | 9 | SM00072 | | | 9 | 001-099 |
| 0452WV | 22 | | GA | | 9-0 | 33-25-23 | SM00052 | | | 9 | SM00072 | | | 9 | 115-199 |
| 0453WG | 22 | | GA | | 7-11 | 33-25-23 | SM00053 | | | 9 | SM00073 | | | 9 | 001-099 |
| 0453WG | 22 | | GA | | 9-0 | 33-25-23 | SM00053 | | | 9 | SM00073 | | | 9 | 115-199 |
| 0455V | 22 | | GA | | 7-11 | 33-25-23 | SM00055 | | | 9 | SM00075 | | | 9 | 001-099 |
| 0455V | 22 | | GA | | 9-0 | 33-25-23 | SM00055 | | | 9 | SM00075 | | | 9 | 115-199 |
| 0456WN | 16 | | GA | | 7-11 | 33-23-23 | SM00056 | | | 9 | SM00076 | | | 9 | 001-099 |
| 0456WN | 16 | | GA | | 9-0 | 33-23-23 | SM00056 | | | 9 | SM00076 | | | 9 | 115-199 |
| 0457W | 20 | | GA | | 7-11 | 33-24-22 | SM00057 | | | 9 | SM00077 | | | 9 | 001-099 |
| 0457W | 20 | | GA | | 9-0 | 33-24-22 | SM00057 | | | 9 | SM00077 | | | 9 | 115-199 |
| 0458WP | 16 | | GA | | 7-11 | 33-23-23 | SM00058 | | | 9 | SM00078 | | | 9 | 001-099 |
| 0458WP | 16 | | GA | | 9-0 | 33-23-23 | SM00058 | | | 9 | SM00078 | | | 9 | 115-199 |
| 0459AJ | 16 | | GA | | 7-11 | 35-21-22 | SM00059 | | | 9 | SM00079 | | | 9 | 001-099 |
| 0459AJ | 16 | | GA | | 9-0 | 35-21-22 | SM00059 | | | 9 | SM00079 | | | 9 | 115-199 |
| 0460K | 18 | | GA | | 7-11 | 35-21-22 | SM00060 | | | 9 | SM00080 | | | 9 | 001-099 |
| 0460K | 18 | | GA | | 9-0 | 35-21-22 | SM00060 | | | 9 | SM00080 | | | 9 | 115-199 |
| 0471G | 16 | | GA | | 7-11 | 33-24-22 | SM00071 | | | 9 | SM00091 | | | 9 | 001-099 |
| 0471G | 16 | | GA | | 7-0 | 33-24-22 | SM00071 | | | 9 | SM00091 | | | 9 | 115-199 |
| 0472WV | 22 | | GA | | 7-11 | 33-25-23 | SM00072 | | | 9 | SM00092 | | | 9 | 001-099 |
| 0472WV | 22 | | GA | | 7-0 | 33-25-23 | SM00072 | | | 9 | SM00092 | | | 9 | 115-199 |
| 0473WG | 22 | | GA | | 7-11 | 33-25-23 | SM00073 | | | 9 | SM00093 | | | 9 | 001-099 |
| 0473WG | 22 | | GA | | 7-0 | 33-25-23 | SM00073 | | | 9 | SM00093 | | | 9 | 115-199 |
| 0475V | 22 | | GA | | 7-11 | 33-25-23 | SM00075 | | | 9 | SM00095 | | | 9 | 001-099 |
| 0475V | 22 | | GA | | 7-0 | 33-25-23 | SM00075 | | | 9 | SM00095 | | | 9 | 115-199 |
| 0476WN | 16 | | GA | | 7-11 | 33-23-23 | SM00076 | | | 9 | SM00096 | | | 9 | 001-099 |
| 0476WN | 16 | | GA | | 7-0 | 33-23-23 | SM00076 | | | 9 | SM00096 | | | 9 | 115-199 |
| 0477W | 20 | | GA | | 7-11 | 33-24-22 | SM00077 | | | 9 | SM00097 | | | 9 | 001-099 |
| 0477W | 20 | | GA | | 7-0 | 33-24-22 | SM00077 | | | 9 | SM00097 | | | 9 | 115-199 |
| 0478WP | 16 | | GA | | 7-11 | 33-23-23 | SM00078 | | | 9 | SM00098 | | | 9 | 001-099 |
| 0478WP | 16 | | GA | | 7-0 | 33-23-23 | SM00078 | | | 9 | SM00098 | | | 9 | 115-199 |
| 0479AJ | 16 | | GA | | 7-11 | 35-21-22 | SM00079 | | | 9 | SM00099 | | | 9 | 001-099 |
| 0479AJ | 16 | | GA | | 7-0 | 35-21-22 | SM00079 | | | 9 | SM00099 | | | 9 | 115-199 |
| 0480K | 18 | | GA | | 7-11 | 35-21-22 | SM00080 | | | 9 | SM00100 | | | 9 | 001-099 |
| 0480K | 18 | | GA | | 7-0 | 35-21-22 | SM00080 | | | 9 | SM00100 | | | 9 | 115-199 |
| 0491G | 16 | | GA | | 8-3 | 33-24-22 | SM00091 | | | 9 | SM00111 | | | 9 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 24

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | 286N3804 | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | | | |
| 0491G | 16 | | GA | | 8-0 | 33-24-22 | SM00091 | | | 9 | SM00111 | | | 9 | 115-199 |
| 0492WV | 22 | | GA | | 8-3 | 33-25-23 | SM00092 | | | 9 | SM00112 | | | 9 | 001-099 |
| 0492WV | 22 | | GA | | 8-0 | 33-25-23 | SM00092 | | | 9 | SM00112 | | | 9 | 115-199 |
| 0493WG | 22 | | GA | | 8-3 | 33-25-23 | SM00093 | | | 9 | SM00113 | | | 9 | 001-099 |
| 0493WG | 22 | | GA | | 8-0 | 33-25-23 | SM00093 | | | 9 | SM00113 | | | 9 | 115-199 |
| 0495V | 22 | | GA | | 8-3 | 33-25-23 | SM00095 | | | 9 | SM00115 | | | 9 | 001-099 |
| 0495V | 22 | | GA | | 8-0 | 33-25-23 | SM00095 | | | 9 | SM00115 | | | 9 | 115-199 |
| 0496WN | 16 | | GA | | 8-3 | 33-23-23 | SM00096 | | | 9 | SM00116 | | | 9 | 001-099 |
| 0496WN | 16 | | GA | | 8-0 | 33-23-23 | SM00096 | | | 9 | SM00116 | | | 9 | 115-199 |
| 0497W | 20 | | GA | | 8-3 | 33-24-22 | SM00097 | | | 9 | SM00117 | | | 9 | 001-099 |
| 0497W | 20 | | GA | | 8-0 | 33-24-22 | SM00097 | | | 9 | SM00117 | | | 9 | 115-199 |
| 0498WP | 16 | | GA | | 8-3 | 33-23-23 | SM00098 | | | 9 | SM00118 | | | 9 | 001-099 |
| 0498WP | 16 | | GA | | 8-0 | 33-23-23 | SM00098 | | | 9 | SM00118 | | | 9 | 115-199 |
| 0499AJ | 16 | | GA | | 8-3 | 35-21-22 | SM00099 | | | 9 | SM00119 | | | 9 | 001-099 |
| 0499AJ | 16 | | GA | | 8-0 | 35-21-22 | SM00099 | | | 9 | SM00119 | | | 9 | 115-199 |
| 0500K | 18 | | GA | | 8-3 | 35-21-22 | SM00100 | | | 9 | SM00120 | | | 9 | 001-099 |
| 0500K | 18 | | GA | | 8-0 | 35-21-22 | SM00100 | | | 9 | SM00120 | | | 9 | 115-199 |
| 0801 | 16 | | GA | | 4-0 | 33-24-22 | D40412P | | 1 | | SM00011 | | | 9 | 001-099 |
| 0801 | 16 | | GA | | 2-0 | 33-24-22 | D40412P | | 1 | | SM00011 | | | 9 | 115-199 |
| 0802 | 22 | | GA | | 4-0 | 33-25-22 | D40412P | | 2 | | SM00012 | | | 9 | 001-099 |
| 0802 | 22 | | GA | | 2-0 | 33-25-22 | D40412P | | 2 | | SM00012 | | | 9 | 115-199 |
| 0803 | 22 | | GA | | 4-0 | 33-25-22 | D40412P | | 3 | | SM00013 | | | 9 | 001-099 |
| 0803 | 22 | | GA | | 2-0 | 33-25-22 | D40412P | | 3 | | SM00013 | | | 9 | 115-199 |
| 0804 | 22 | | GA | | 4-0 | 33-25-22 | D40412P | | 4 | | SM00014 | | | 9 | 001-099 |
| 0804 | 22 | | GA | | 2-0 | 33-25-22 | D40412P | | 4 | | SM00014 | | | 9 | 115-199 |
| 0805 | 22 | | GA | | 4-0 | 33-25-22 | D40412P | | 5 | | SM00015 | | | 9 | 001-099 |
| 0805 | 22 | | GA | | 2-0 | 33-25-22 | D40412P | | 5 | | SM00015 | | | 9 | 115-199 |
| 0807 | 20 | | GA | | 4-0 | 33-24-22 | D40412P | | 7 | | SM00017 | | | 9 | 001-099 |
| 0807 | 20 | | GA | | 2-0 | 33-24-22 | D40412P | | 7 | | SM00017 | | | 9 | 115-199 |
| 0811 | 16 | | GA | | 3-6 | 33-24-22 | D40414J | | 1 | | SM00111 | | | 9 | 001-099 |
| 0811 | 16 | | GA | | 3-0 | 33-24-22 | D40414J | | 1 | | SM00111 | | | 9 | 115-199 |
| 0812 | 22 | | GA | | 3-6 | 33-25-23 | D40414J | | 2 | | SM00112 | | | 9 | 001-099 |
| 0812 | 22 | | GA | | 3-0 | 33-25-23 | D40414J | | 2 | | SM00112 | | | 9 | 115-199 |
| 0813 | 22 | | GA | | 3-6 | 33-25-23 | D40414J | | 3 | | SM00113 | | | 9 | 001-099 |
| 0813 | 22 | | GA | | 3-0 | 33-25-23 | D40414J | | 3 | | SM00113 | | | 9 | 115-199 |
| 0815 | 22 | | GA | | 3-6 | 33-25-23 | D40414J | | 5 | | SM00115 | | | 9 | 001-099 |
| 0815 | 22 | | GA | | 3-0 | 33-25-23 | D40414J | | 5 | | SM00115 | | | 9 | 115-199 |
| 0816 | 16 | | GA | | 3-6 | 33-23-23 | D40414J | | 6 | | SM00116 | | | 9 | 001-099 |
| 0816 | 16 | | GA | | 3-0 | 33-23-23 | D40414J | | 6 | | SM00116 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 25

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | |
| 0817 | 20 | GA | | | 3-6 | 33-24-22 | D40414J | | 7 | | SM00117 | | 9 | | 001-099 |
| 0817 | 20 | GA | | | 3-0 | 33-24-22 | D40414J | | 7 | | SM00117 | | 9 | | 115-199 |
| 0818 | 16 | GA | | | 3-6 | 33-23-23 | D40414J | | 8 | | SM00118 | | 9 | | 001-099 |
| 0818 | 16 | GA | | | 3-0 | 33-23-23 | D40414J | | 8 | | SM00118 | | 9 | | 115-199 |
| 0819 | 16 | GA | | | 3-6 | 35-21-22 | D40414J | | 9 | | SM00119 | | 9 | | 001-099 |
| 0819 | 16 | GA | | | 3-0 | 35-21-22 | D40414J | | 9 | | SM00119 | | 9 | | 115-199 |
| 0820 | 18 | GA | | | 3-6 | 35-21-22 | D40414J | | 10 | | SM00120 | | 9 | | 001-099 |
| 0820 | 18 | GA | | | 3-0 | 35-21-22 | D40414J | | 10 | | SM00120 | | 9 | | 115-199 |
| 0822 | 16 | GA | | | 25-7 | SPARE | D40412P | | 22 | | D40414J | 19 | | | 001-099 |
| 0822 | 16 | GA | | | 26-0 | SPARE | D40412P | | 22 | | D40414J | 19 | | | 115-199 |
| 0825 | 22 | GA | | | 9-8 | 33-25-23 | D40412P | | 25 | | SM00055 | | 9 | | 001-099 |
| 0825 | 22 | GA | | | 8-0 | 33-25-23 | D40412P | | 25 | | SM00055 | | 9 | | 115-199 |
| 0827 | 20 | GA | | | 18-11 | 33-23-23 | D40412P | | 27 | | T10017 | HV3 | E | | 001-099 |
| 0827 | 20 | GA | | | 20-0 | 33-23-23 | D40412P | | 27 | | T10017 | HV3 | E | | 115-199 |
| 0828 | 20 | GA | | | 25-7 | 33-23-24 | D40412P | | 28 | | D40414J | 18 | | | 001-099 |
| 0828 | 20 | GA | | | 26-0 | 33-23-24 | D40412P | | 28 | | D40414J | 18 | | | 115-199 |
| 0829 | 16 | GA | | | 9-8 | 35-21-22 | D40412P | | 29 | | SM00059 | | 9 | | 001-099 |
| 0829 | 16 | GA | | | 8-0 | 35-21-22 | D40412P | | 29 | | SM00059 | | 9 | | 115-199 |
| 0835 | 22 | GA | | | 25-7 | 23-31-41 | D40412P | | 15 | | D40414J | 15 | | | 001-099 |
| 0835 | 22 | GA | | | 26-0 | 23-31-41 | D40412P | | 15 | | D40414J | 15 | | | 115-199 |
| 0836 | 16 | GA | | | 4-0 | 33-23-22 | D40412P | | 36 | | SM00016 | | 9 | | 001-099 |
| 0836 | 16 | GA | | | 2-0 | 33-23-22 | D40412P | | 36 | | SM00016 | | 9 | | 115-199 |
| 0838 | 16 | GA | | | 4-0 | 33-23-22 | D40412P | | 38 | | SM00018 | | 9 | | 001-099 |
| 0838 | 16 | GA | | | 2-0 | 33-23-22 | D40412P | | 38 | | SM00018 | | 9 | | 115-199 |
| 0839 | 16 | GA | | | 4-0 | 35-21-21 | D40412P | | 39 | | SM00019 | | 9 | | 001-099 |
| 0839 | 16 | GA | | | 2-0 | 35-21-21 | D40412P | | 39 | | SM00019 | | 9 | | 115-199 |
| 0840 | 18 | GA | | | 4-0 | 35-21-21 | D40412P | | 40 | | SM00020 | | 9 | | 001-099 |
| 0840 | 18 | GA | | | 2-0 | 35-21-21 | D40412P | | 40 | | SM00020 | | 9 | | 115-199 |
| 0842 | 14 | GA | | | 6-4 | 33-23-23 | T10017 | GND | E | | GD03253 | AC.. | E | | 001-099 |
| 0842 | 14 | GA | | | 7-0 | 33-23-23 | T10017 | GND | E | | GD03253 | AC.. | E | | 115-199 |
| 0846 | 16 | GA | | | 7-9 | 33-23-23 | T10017 | LV | E | | SM00076 | | 9 | | 001-099 |
| 0846 | 16 | GA | | | 7-0 | 33-23-23 | T10017 | LV | E | | SM00076 | | 9 | | 115-199 |
| 0911 | 20 | GA | | | 25-7 | SPARE | D40412P | | 11 | | D40414J | 11 | | | 001-099 |
| 0911 | 20 | GA | | | 26-0 | SPARE | D40412P | | 11 | | D40414J | 11 | | | 115-199 |
| 0918 | 16 | GA | | | 6-2 | 33-23-22 | SM00018 | | 9 | | GD03275 | AC.. | E | | 001-099 |
| 0918 | 16 | GA | | | 4-0 | 33-23-22 | SM00018 | | 9 | | GD03275 | AC.. | E | | 115-199 |
| 0919 | 22 | GA | | | 2-0 | 33-25-22 | D40412P | | 9 | | SM06019 | | 9 | | 115-199 |
| 0920 | 18 | GA | | | 5-3 | 35-21-21 | SM00020 | | 9 | | GD03271 | DC.. | E | | 001-099 |
| 0920 | 18 | GA | | | 4-0 | 35-21-21 | SM00020 | | 9 | | GD03271 | DC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 26

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|-------|-----|---------------------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W3804 | 286N3804 | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | | | | |
| 0921 | 16 | GA | | 10-6 | 33-23-22 | SM00038 | | | 9 | | GD03185 | AC.. | E | | 001-099 | |
| 0921 | 16 | GA | | 11-0 | 33-23-22 | SM00038 | | | 9 | | GD03185 | AC.. | E | | 115-199 | |
| 0922 | 16 | GA | | 5-3 | 33-23-23 | SM00098 | | | 9 | | GD03187 | AC.. | E | | 001-099 | |
| 0922 | 16 | GA | | 5-0 | 33-23-23 | SM00098 | | | 9 | | GD03187 | AC.. | E | | 115-199 | |
| 0928 | 16 | GA | | 3-2 | 33-23-23 | SM00058 | | | 9 | | GD03277 | AC.. | E | | 001-099 | |
| 0928 | 16 | GA | | 4-0 | 33-23-23 | SM00058 | | | 9 | | GD03277 | AC.. | E | | 115-199 | |
| 0930 | 18 | GA | | 3-8 | 35-21-22 | SM00080 | | | 9 | | GD03183 | DC.. | E | | 001-099 | |
| 0930 | 18 | GA | | 4-0 | 35-21-22 | SM00080 | | | 9 | | GD03183 | DC.. | E | | 115-199 | |
| 0940 | 22 | GA | | 5-1 | 33-25-23 | SM00053 | | | 9 | | SP00540 | | 9 | | 001-099 | |
| 2011B | 22 | GB | A | 8-8 | 23-31-32 | D06046 | | 14 | | | SM00024 | | 9 | | 001-099 | |
| 2011B | 22 | GB | A | 8-0 | 23-31-32 | D06046 | | 13 | | | SM00023 | | 9 | | 115-199 | |
| 2011R | 22 | GB | A | 0-0 | 23-31-32 | D06046 | | 13 | | | SM00023 | | 9 | | 001-099 | |
| 2011R | 22 | GB | A | 0-0 | 23-31-32 | D06046 | | 14 | | | SM00024 | | 9 | | 115-199 | |
| 2021B | 22 | GB | B | 8-1 | 23-31-32 | D06048 | | 14 | | | SM00024 | | 9 | | 001-099 | |
| 2021B | 22 | GB | B | 9-0 | 23-31-32 | D06048 | | 13 | | | SM00023 | | 9 | | 115-199 | |
| 2021R | 22 | GB | B | 0-0 | 23-31-32 | D06048 | | 13 | | | SM00023 | | 9 | | 001-099 | |
| 2021R | 22 | GB | B | 0-0 | 23-31-32 | D06048 | | 14 | | | SM00024 | | 9 | | 115-199 | |
| 2023B | 22 | GB | L | 5-1 | 23-31-32 | SM00024 | | | 9 | | SM00044 | | 9 | | 001-099 | |
| 2023B | 22 | GB | L | 4-0 | 23-31-32 | SM00023 | | | 9 | | SM00043 | | 9 | | 115-199 | |
| 2023R | 22 | GB | L | 0-0 | 23-31-32 | SM00023 | | | 9 | | SM00043 | | 9 | | 001-099 | |
| 2023R | 22 | GB | L | 0-0 | 23-31-32 | SM00024 | | | 9 | | SM00044 | | 9 | | 115-199 | |
| 2031B | 22 | GB | C | 8-0 | 23-31-32 | D06050 | | 14 | | | SM00044 | | 9 | | 001-099 | |
| 2031B | 22 | GB | C | 10-0 | 23-31-32 | D06050 | | 13 | | | SM00043 | | 9 | | 115-199 | |
| 2031R | 22 | GB | C | 0-0 | 23-31-32 | D06050 | | 13 | | | SM00043 | | 9 | | 001-099 | |
| 2031R | 22 | GB | C | 0-0 | 23-31-32 | D06050 | | 14 | | | SM00044 | | 9 | | 115-199 | |
| 2041B | 22 | GB | D | 10-11 | 23-31-32 | D06052 | | 14 | | | SM00044 | | 9 | | 001-099 | |
| 2041B | 22 | GB | D | 13-0 | 23-31-32 | D06052 | | 13 | | | SM00043 | | 9 | | 115-199 | |
| 2041R | 22 | GB | D | 0-0 | 23-31-32 | D06052 | | 13 | | | SM00043 | | 9 | | 001-099 | |
| 2041R | 22 | GB | D | 0-0 | 23-31-32 | D06052 | | 14 | | | SM00044 | | 9 | | 115-199 | |
| 2043B | 22 | GB | M | 6-6 | 23-31-32 | SM00044 | | | 9 | | SM00064 | | 9 | | 001-099 | |
| 2043B | 22 | GB | M | 5-0 | 23-31-32 | SM00043 | | | 9 | | SM00063 | | 9 | | 115-199 | |
| 2043R | 22 | GB | M | 0-0 | 23-31-32 | SM00043 | | | 9 | | SM00063 | | 9 | | 001-099 | |
| 2043R | 22 | GB | M | 0-0 | 23-31-32 | SM00044 | | | 9 | | SM00064 | | 9 | | 115-199 | |
| 2051B | 22 | GB | E | 8-11 | 23-31-32 | D06054 | | 14 | | | SM00064 | | 9 | | 001-099 | |
| 2051B | 22 | GB | E | 11-0 | 23-31-32 | D06054 | | 13 | | | SM00063 | | 9 | | 115-199 | |
| 2051R | 22 | GB | E | 0-0 | 23-31-32 | D06054 | | 13 | | | SM00063 | | 9 | | 001-099 | |
| 2051R | 22 | GB | E | 0-0 | 23-31-32 | D06054 | | 14 | | | SM00064 | | 9 | | 115-199 | |
| 2061B | 22 | GB | F | 9-4 | 23-31-32 | D06056 | | 14 | | | SM00064 | | 9 | | 001-099 | |
| 2061B | 22 | GB | F | 12-0 | 23-31-32 | D06056 | | 13 | | | SM00063 | | 9 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 27

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | | To | | | | | |
|------------|-------------|----|-------|---------------------------------------|-------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | 286N3804 | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | | | | |
| 2061R | 22 | GB | F | | 0-0 | 23-31-32 | D06056 | 13 | | | | SM00063 | 9 | | | 001-099 |
| 2061R | 22 | GB | F | | 0-0 | 23-31-32 | D06056 | 14 | | | | SM00064 | 9 | | | 115-199 |
| 2063B | 22 | GB | N | | 7-11 | 23-31-32 | SM00064 | | 9 | | | SM00084 | 9 | | | 001-099 |
| 2063B | 22 | GB | N | | 9-0 | 23-31-32 | SM00063 | | 9 | | | SM00083 | 9 | | | 115-199 |
| 2063R | 22 | GB | N | | 0-0 | 23-31-32 | SM00063 | | 9 | | | SM00083 | 9 | | | 001-099 |
| 2063R | 22 | GB | N | | 0-0 | 23-31-32 | SM00064 | | 9 | | | SM00084 | 9 | | | 115-199 |
| 2071B | 22 | GB | G | | 9-11 | 23-31-32 | D06058 | 14 | | | | SM00084 | 9 | | | 001-099 |
| 2071B | 22 | GB | G | | 9-0 | 23-31-32 | D06058 | 13 | | | | SM00083 | 9 | | | 115-199 |
| 2071R | 22 | GB | G | | 0-0 | 23-31-32 | D06058 | 13 | | | | SM00083 | 9 | | | 001-099 |
| 2071R | 22 | GB | G | | 0-0 | 23-31-32 | D06058 | 14 | | | | SM00084 | 9 | | | 115-199 |
| 2081B | 22 | GB | H | | 11-10 | 23-31-32 | D06060 | 14 | | | | SM00084 | 9 | | | 001-099 |
| 2081B | 22 | GB | H | | 12-0 | 23-31-32 | D06060 | 13 | | | | SM00083 | 9 | | | 115-199 |
| 2081R | 22 | GB | H | | 0-0 | 23-31-32 | D06060 | 13 | | | | SM00083 | 9 | | | 001-099 |
| 2081R | 22 | GB | H | | 0-0 | 23-31-32 | D06060 | 14 | | | | SM00084 | 9 | | | 115-199 |
| 2083B | 22 | GB | O | | 7-11 | 23-31-32 | SM00084 | | 9 | | | SM00104 | 9 | | | 001-099 |
| 2083B | 22 | GB | O | | 7-0 | 23-31-32 | SM00083 | | 9 | | | SM00103 | 9 | | | 115-199 |
| 2083R | 22 | GB | O | | 0-0 | 23-31-32 | SM00083 | | 9 | | | SM00103 | 9 | | | 001-099 |
| 2083R | 22 | GB | O | | 0-0 | 23-31-32 | SM00084 | | 9 | | | SM00104 | 9 | | | 115-199 |
| 2091B | 22 | GB | I | | 8-9 | 23-31-32 | D06062 | 14 | | | | SM00104 | 9 | | | 001-099 |
| 2091B | 22 | GB | I | | 8-0 | 23-31-32 | D06062 | 13 | | | | SM00103 | 9 | | | 115-199 |
| 2091R | 22 | GB | I | | 0-0 | 23-31-32 | D06062 | 13 | | | | SM00103 | 9 | | | 001-099 |
| 2091R | 22 | GB | I | | 0-0 | 23-31-32 | D06062 | 14 | | | | SM00104 | 9 | | | 115-199 |
| 2101B | 22 | GB | J | | 10-3 | 23-31-32 | D06064 | 14 | | | | SM00104 | 9 | | | 001-099 |
| 2101B | 22 | GB | J | | 10-0 | 23-31-32 | D06064 | 13 | | | | SM00103 | 9 | | | 115-199 |
| 2101R | 22 | GB | J | | 0-0 | 23-31-32 | D06064 | 13 | | | | SM00103 | 9 | | | 001-099 |
| 2101R | 22 | GB | J | | 0-0 | 23-31-32 | D06064 | 14 | | | | SM00104 | 9 | | | 115-199 |
| 2103B | 22 | GB | T | | 8-3 | 23-31-32 | SM00104 | | 9 | | | SM00124 | 9 | | | 001-099 |
| 2103B | 22 | GB | T | | 8-0 | 23-31-32 | SM00103 | | 9 | | | SM00123 | 9 | | | 115-199 |
| 2103R | 22 | GB | T | | 0-0 | 23-31-32 | SM00103 | | 9 | | | SM00123 | 9 | | | 001-099 |
| 2103R | 22 | GB | T | | 0-0 | 23-31-32 | SM00104 | | 9 | | | SM00124 | 9 | | | 115-199 |
| 2111B | 22 | GB | K | | 8-4 | 23-31-32 | D06066 | 14 | | | | SM00124 | 9 | | | 001-099 |
| 2111B | 22 | GB | K | | 9-0 | 23-31-32 | D06066 | 13 | | | | SM00123 | 9 | | | 115-199 |
| 2111R | 22 | GB | K | | 0-0 | 23-31-32 | D06066 | 13 | | | | SM00123 | 9 | | | 001-099 |
| 2111R | 22 | GB | K | | 0-0 | 23-31-32 | D06066 | 14 | | | | SM00124 | 9 | | | 115-199 |
| 2413B | 22 | GB | Q | | 3-2 | 23-31-32 | D40412P | 14 | | | | SM00024 | 9 | | | 001-099 |
| 2413B | 22 | GB | Q | | 2-0 | 23-31-32 | D40412P | 13 | | | | SM00023 | 9 | | | 115-199 |
| 2413R | 22 | GB | Q | | 0-0 | 23-31-32 | D40412P | 13 | | | | SM00023 | 9 | | | 001-099 |
| 2413R | 22 | GB | Q | | 0-0 | 23-31-32 | D40412P | 14 | | | | SM00024 | 9 | | | 115-199 |
| 2423B | 22 | GB | R | | 3-6 | 23-31-32 | D40414J | 14 | | | | SM00124 | 9 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 28

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3804 | 286N3804 | | | | PSU HARNESS-RIGHT, CENTER (continued) | | | | | | | | | | |
| 2423B | 22 | | GB | R | 4-0 | 23-31-32 | D40414J | 13 | | | SM00123 | | 9 | | 115-199 |
| 2423R | 22 | | GB | R | 0-0 | 23-31-32 | D40414J | 13 | | | SM00123 | | 9 | | 001-099 |
| 2423R | 22 | | GB | R | 0-0 | 23-31-32 | D40414J | 14 | | | SM00124 | | 9 | | 115-199 |
| 6019AD | 22 | | GA | | 8-0 | 33-25-22 | D06046 | 9 | | | SM06019 | | 9 | | 115-199 |
| 6029AD | 22 | | GA | | 8-0 | 33-25-22 | D06048 | 9 | | | SM06019 | | 9 | | 115-199 |
| 6039AD | 22 | | GA | | 9-0 | 33-25-22 | D06050 | 9 | | | SM06039 | | 9 | | 115-199 |
| 6049AD | 22 | | GA | | 13-0 | 33-25-22 | D06052 | 9 | | | SM06039 | | 9 | | 115-199 |
| 6519AD | 22 | | GA | | 4-0 | 33-25-22 | SM06019 | | 9 | | SM06039 | | 9 | | 115-199 |
| W3806 | 286N3806 | | | | PSU HARNESS-RIGHT, AFT | | | | | | | | | | |
| 0011G | 16 | | GA | | 7-2 | 33-24-23 | D06068 | 1 | | | SM00011 | | 9 | | 001-099 |
| 0011G | 16 | | GA | | 8-0 | 33-24-23 | D06068 | 1 | | | SM00011 | | 9 | | 115-199 |
| 0012WV | 22 | | GA | | 7-2 | 33-25-24 | D06068 | 2 | | | SM00012 | | 9 | | 001-099 |
| 0012WV | 22 | | GA | | 8-0 | 33-25-24 | D06068 | 2 | | | SM00012 | | 9 | | 115-199 |
| 0013WG | 22 | | GA | | 7-2 | 33-25-24 | D06068 | 3 | | | SM00013 | | 9 | | 001-099 |
| 0013WG | 22 | | GA | | 8-0 | 33-25-24 | D06068 | 3 | | | SM00013 | | 9 | | 115-199 |
| 0015V | 22 | | GA | | 7-2 | 33-25-24 | D06068 | 5 | | | SM00015 | | 9 | | 001-099 |
| 0015V | 22 | | GA | | 8-0 | 33-25-24 | D06068 | 5 | | | SM00015 | | 9 | | 115-199 |
| 0016WN | 16 | | GA | | 7-2 | 33-23-23 | D06068 | 6 | | | SM00016 | | 9 | | 001-099 |
| 0016WN | 16 | | GA | | 8-0 | 33-23-23 | D06068 | 6 | | | SM00016 | | 9 | | 115-199 |
| 0017W | 20 | | GA | | 7-2 | 33-24-23 | D06068 | 7 | | | SM00017 | | 9 | | 001-099 |
| 0017W | 20 | | GA | | 8-0 | 33-24-23 | D06068 | 7 | | | SM00017 | | 9 | | 115-199 |
| 0018WP | 16 | | GA | | 7-2 | 33-23-23 | D06068 | 8 | | | SM00018 | | 9 | | 001-099 |
| 0018WP | 16 | | GA | | 8-0 | 33-23-23 | D06068 | 8 | | | SM00018 | | 9 | | 115-199 |
| 0019AJ | 20 | | GA | | 7-2 | 35-21-22 | D06068 | 11 | | | SM00019 | | 9 | | 001-099 |
| 0019AJ | 20 | | GA | | 8-0 | 35-21-22 | D06068 | 11 | | | SM00019 | | 9 | | 115-199 |
| 0020K | 18 | | GA | | 7-2 | 35-21-22 | D06068 | 10 | | | SM00020 | | 9 | | 001-099 |
| 0020K | 18 | | GA | | 8-0 | 35-21-22 | D06068 | 10 | | | SM00020 | | 9 | | 115-199 |
| 0021G | 16 | | GA | | 9-1 | 33-24-23 | D06070 | 1 | | | SM00011 | | 9 | | 001-099 |
| 0021G | 16 | | GA | | 10-0 | 33-24-23 | D06070 | 1 | | | SM00011 | | 9 | | 115-199 |
| 0022WV | 22 | | GA | | 9-1 | 33-25-24 | D06070 | 2 | | | SM00012 | | 9 | | 001-099 |
| 0022WV | 22 | | GA | | 10-0 | 33-25-24 | D06070 | 2 | | | SM00012 | | 9 | | 115-199 |
| 0023WG | 22 | | GA | | 9-1 | 33-25-24 | D06070 | 3 | | | SM00013 | | 9 | | 001-099 |
| 0023WG | 22 | | GA | | 10-0 | 33-25-24 | D06070 | 3 | | | SM00013 | | 9 | | 115-199 |
| 0025V | 22 | | GA | | 9-1 | 33-25-24 | D06070 | 5 | | | SM00015 | | 9 | | 001-099 |
| 0025V | 22 | | GA | | 10-0 | 33-25-24 | D06070 | 5 | | | SM00015 | | 9 | | 115-199 |
| 0026WN | 16 | | GA | | 9-1 | 33-23-23 | D06070 | 6 | | | SM00016 | | 9 | | 001-099 |
| 0026WN | 16 | | GA | | 10-0 | 33-23-23 | D06070 | 6 | | | SM00016 | | 9 | | 115-199 |
| 0027W | 20 | | GA | | 9-1 | 33-24-23 | D06070 | 7 | | | SM00017 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 29

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | |
| 0027W | 20 | GA | | | 10-0 | 33-24-23 | D06070 | | | | SM00017 | | | 9 | 115-199 |
| 0028WP | 16 | GA | | | 9-1 | 33-23-23 | D06070 | | | | SM00018 | | | 9 | 001-099 |
| 0028WP | 16 | GA | | | 10-0 | 33-23-23 | D06070 | | | | SM00018 | | | 9 | 115-199 |
| 0029AJ | 20 | GA | | | 9-1 | 35-21-22 | D06070 | | | | SM00019 | | | 9 | 001-099 |
| 0029AJ | 20 | GA | | | 10-0 | 35-21-22 | D06070 | | | | SM00019 | | | 9 | 115-199 |
| 0030K | 18 | GA | | | 9-1 | 35-21-22 | D06070 | | | | SM00020 | | | 9 | 001-099 |
| 0030K | 18 | GA | | | 10-0 | 35-21-22 | D06070 | | | | SM00020 | | | 9 | 115-199 |
| 0031G | 16 | GA | | | 8-0 | 33-24-23 | D06072 | | | | SM00031 | | | 9 | 001-099 |
| 0031G | 16 | GA | | | 9-0 | 33-24-23 | D06072 | | | | SM00031 | | | 9 | 115-199 |
| 0032WV | 22 | GA | | | 8-0 | 33-25-24 | D06072 | | | | SM00032 | | | 9 | 001-099 |
| 0032WV | 22 | GA | | | 9-0 | 33-25-24 | D06072 | | | | SM00032 | | | 9 | 115-199 |
| 0033WG | 22 | GA | | | 8-0 | 33-25-24 | D06072 | | | | SM00033 | | | 9 | 001-099 |
| 0033WG | 22 | GA | | | 9-0 | 33-25-24 | D06072 | | | | SM00033 | | | 9 | 115-199 |
| 0035V | 22 | GA | | | 8-0 | 33-25-24 | D06072 | | | | SM00035 | | | 9 | 001-099 |
| 0035V | 22 | GA | | | 9-0 | 33-25-24 | D06072 | | | | SM00035 | | | 9 | 115-199 |
| 0036WN | 16 | GA | | | 8-0 | 33-23-23 | D06072 | | | | SM00036 | | | 9 | 001-099 |
| 0036WN | 16 | GA | | | 9-0 | 33-23-23 | D06072 | | | | SM00036 | | | 9 | 115-199 |
| 0037W | 20 | GA | | | 8-0 | 33-24-23 | D06072 | | | | SM00037 | | | 9 | 001-099 |
| 0037W | 20 | GA | | | 9-0 | 33-24-23 | D06072 | | | | SM00037 | | | 9 | 115-199 |
| 0038WP | 16 | GA | | | 8-0 | 33-23-23 | D06072 | | | | SM00038 | | | 9 | 001-099 |
| 0038WP | 16 | GA | | | 9-0 | 33-23-23 | D06072 | | | | SM00038 | | | 9 | 115-199 |
| 0039AJ | 20 | GA | | | 8-0 | 35-21-22 | D06072 | | | | SM00039 | | | 9 | 001-099 |
| 0039AJ | 20 | GA | | | 9-0 | 35-21-22 | D06072 | | | | SM00039 | | | 9 | 115-199 |
| 0040K | 18 | GA | | | 8-0 | 35-21-22 | D06072 | | | | SM00040 | | | 9 | 001-099 |
| 0040K | 18 | GA | | | 9-0 | 35-21-22 | D06072 | | | | SM00040 | | | 9 | 115-199 |
| 0041G | 16 | GA | | | 9-4 | 33-24-23 | D06074 | | | | SM00031 | | | 9 | 001-099 |
| 0041G | 16 | GA | | | 10-0 | 33-24-23 | D06074 | | | | SM00031 | | | 9 | 115-199 |
| 0042WV | 22 | GA | | | 9-4 | 33-25-24 | D06074 | | | | SM00032 | | | 9 | 001-099 |
| 0042WV | 22 | GA | | | 10-0 | 33-25-24 | D06074 | | | | SM00032 | | | 9 | 115-199 |
| 0043WG | 22 | GA | | | 9-4 | 33-25-24 | D06074 | | | | SM00033 | | | 9 | 001-099 |
| 0043WG | 22 | GA | | | 10-0 | 33-25-24 | D06074 | | | | SM00033 | | | 9 | 115-199 |
| 0045V | 22 | GA | | | 9-4 | 33-25-24 | D06074 | | | | SM00035 | | | 9 | 001-099 |
| 0045V | 22 | GA | | | 10-0 | 33-25-24 | D06074 | | | | SM00035 | | | 9 | 115-199 |
| 0046WN | 16 | GA | | | 9-4 | 33-23-23 | D06074 | | | | SM00036 | | | 9 | 001-099 |
| 0046WN | 16 | GA | | | 10-0 | 33-23-23 | D06074 | | | | SM00036 | | | 9 | 115-199 |
| 0047W | 20 | GA | | | 9-4 | 33-24-23 | D06074 | | | | SM00037 | | | 9 | 001-099 |
| 0047W | 20 | GA | | | 10-0 | 33-24-23 | D06074 | | | | SM00037 | | | 9 | 115-199 |
| 0048WP | 16 | GA | | | 9-4 | 33-23-23 | D06074 | | | | SM00038 | | | 9 | 001-099 |
| 0048WP | 16 | GA | | | 10-0 | 33-23-23 | D06074 | | | | SM00038 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 30

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|------------------------------------|----------|--------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3806 | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | |
| 0049AJ | 20 | | GA | | 9-4 | 35-21-22 | D06074 | | 11 | | | SM00039 | | 9 | | 001-099 |
| 0049AJ | 20 | | GA | | 10-0 | 35-21-22 | D06074 | | 11 | | | SM00039 | | 9 | | 115-199 |
| 0050K | 18 | | GA | | 9-4 | 35-21-22 | D06074 | | 10 | | | SM00040 | | 9 | | 001-099 |
| 0050K | 18 | | GA | | 10-0 | 35-21-22 | D06074 | | 10 | | | SM00040 | | 9 | | 115-199 |
| 0051G | 16 | | GA | | 7-7 | 33-24-23 | D06076 | | 1 | | | SM00051 | | 9 | | 001-099 |
| 0051G | 16 | | GA | | 8-0 | 33-24-23 | D06076 | | 1 | | | SM00051 | | 9 | | 115-199 |
| 0052WV | 22 | | GA | | 7-7 | 33-25-24 | D06076 | | 2 | | | SM00052 | | 9 | | 001-099 |
| 0052WV | 22 | | GA | | 8-0 | 33-25-24 | D06076 | | 2 | | | SM00052 | | 9 | | 115-199 |
| 0053WG | 22 | | GA | | 7-7 | 33-25-24 | D06076 | | 3 | | | SM00053 | | 9 | | 001-099 |
| 0053WG | 22 | | GA | | 8-0 | 33-25-24 | D06076 | | 3 | | | SM00053 | | 9 | | 115-199 |
| 0055V | 22 | | GA | | 7-7 | 33-25-24 | D06076 | | 5 | | | SM00055 | | 9 | | 001-099 |
| 0055V | 22 | | GA | | 8-0 | 33-25-24 | D06076 | | 5 | | | SM00055 | | 9 | | 115-199 |
| 0056WN | 16 | | GA | | 7-7 | 33-23-24 | D06076 | | 6 | | | SM00056 | | 9 | | 001-099 |
| 0056WN | 16 | | GA | | 8-0 | 33-23-24 | D06076 | | 6 | | | SM00056 | | 9 | | 115-199 |
| 0057W | 20 | | GA | | 7-7 | 33-24-23 | D06076 | | 7 | | | SM00057 | | 9 | | 001-099 |
| 0057W | 20 | | GA | | 8-0 | 33-24-23 | D06076 | | 7 | | | SM00057 | | 9 | | 115-199 |
| 0058WP | 16 | | GA | | 7-7 | 33-23-24 | D06076 | | 8 | | | SM00058 | | 9 | | 001-099 |
| 0058WP | 16 | | GA | | 8-0 | 33-23-24 | D06076 | | 8 | | | SM00058 | | 9 | | 115-199 |
| 0059AJ | 20 | | GA | | 7-7 | 35-21-22 | D06076 | | 11 | | | SM00059 | | 9 | | 001-099 |
| 0059AJ | 20 | | GA | | 8-0 | 35-21-22 | D06076 | | 11 | | | SM00059 | | 9 | | 115-199 |
| 0060K | 18 | | GA | | 7-7 | 35-21-22 | D06076 | | 10 | | | SM00060 | | 9 | | 001-099 |
| 0060K | 18 | | GA | | 8-0 | 35-21-22 | D06076 | | 10 | | | SM00060 | | 9 | | 115-199 |
| 0061G | 16 | | GA | | 11-9 | 33-24-23 | D06078 | | 1 | | | SM00051 | | 9 | | 001-099 |
| 0061G | 16 | | GA | | 12-0 | 33-24-23 | D06078 | | 1 | | | SM00051 | | 9 | | 115-199 |
| 0062WV | 22 | | GA | | 11-9 | 33-25-24 | D06078 | | 2 | | | SM00052 | | 9 | | 001-099 |
| 0062WV | 22 | | GA | | 12-0 | 33-25-24 | D06078 | | 2 | | | SM00052 | | 9 | | 115-199 |
| 0063WG | 22 | | GA | | 11-9 | 33-25-24 | D06078 | | 3 | | | SM00053 | | 9 | | 001-099 |
| 0063WG | 22 | | GA | | 12-0 | 33-25-24 | D06078 | | 3 | | | SM00053 | | 9 | | 115-199 |
| 0065V | 22 | | GA | | 11-9 | 33-25-24 | D06078 | | 5 | | | SM00055 | | 9 | | 001-099 |
| 0065V | 22 | | GA | | 12-0 | 33-25-24 | D06078 | | 5 | | | SM00055 | | 9 | | 115-199 |
| 0066WN | 16 | | GA | | 11-9 | 33-23-24 | D06078 | | 6 | | | SM00056 | | 9 | | 001-099 |
| 0066WN | 16 | | GA | | 12-0 | 33-23-24 | D06078 | | 6 | | | SM00056 | | 9 | | 115-199 |
| 0067W | 20 | | GA | | 11-9 | 33-24-23 | D06078 | | 7 | | | SM00057 | | 9 | | 001-099 |
| 0067W | 20 | | GA | | 12-0 | 33-24-23 | D06078 | | 7 | | | SM00057 | | 9 | | 115-199 |
| 0068WP | 16 | | GA | | 11-9 | 33-23-24 | D06078 | | 8 | | | SM00058 | | 9 | | 001-099 |
| 0068WP | 16 | | GA | | 12-0 | 33-23-24 | D06078 | | 8 | | | SM00058 | | 9 | | 115-199 |
| 0069AJ | 20 | | GA | | 11-9 | 35-21-22 | D06078 | | 11 | | | SM00059 | | 9 | | 001-099 |
| 0069AJ | 20 | | GA | | 12-0 | 35-21-22 | D06078 | | 11 | | | SM00059 | | 9 | | 115-199 |
| 0070K | 18 | | GA | | 11-9 | 35-21-22 | D06078 | | 10 | | | SM00060 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 31

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | |
| 0070K | 18 | GA | | | 12-0 | 35-21-22 | D06078 | 10 | | | SM00060 | 9 | | | 115-199 |
| 0071G | 16 | GA | | | 8-10 | 33-24-23 | D06080 | 1 | | | SM00071 | 9 | | | 001-099 |
| 0071G | 16 | GA | | | 9-0 | 33-24-23 | D06080 | 1 | | | SM00071 | 9 | | | 115-199 |
| 0072WV | 22 | GA | | | 8-10 | 33-25-24 | D06080 | 2 | | | SM00072 | 9 | | | 001-099 |
| 0072WV | 22 | GA | | | 9-0 | 33-25-24 | D06080 | 2 | | | SM00072 | 9 | | | 115-199 |
| 0073WG | 22 | GA | | | 8-10 | 33-25-24 | D06080 | 3 | | | SM00073 | 9 | | | 001-099 |
| 0073WG | 22 | GA | | | 9-0 | 33-25-24 | D06080 | 3 | | | SM00073 | 9 | | | 115-199 |
| 0075V | 22 | GA | | | 8-10 | 33-25-24 | D06080 | 5 | | | SM00075 | 9 | | | 001-099 |
| 0075V | 22 | GA | | | 9-0 | 33-25-24 | D06080 | 5 | | | SM00075 | 9 | | | 115-199 |
| 0076WN | 16 | GA | | | 8-10 | 33-23-24 | D06080 | 6 | | | SM00076 | 9 | | | 001-099 |
| 0076WN | 16 | GA | | | 9-0 | 33-23-24 | D06080 | 6 | | | SM00076 | 9 | | | 115-199 |
| 0077W | 20 | GA | | | 8-10 | 33-24-23 | D06080 | 7 | | | SM00077 | 9 | | | 001-099 |
| 0077W | 20 | GA | | | 9-0 | 33-24-23 | D06080 | 7 | | | SM00077 | 9 | | | 115-199 |
| 0078WP | 16 | GA | | | 8-10 | 33-23-24 | D06080 | 8 | | | SM00078 | 9 | | | 001-099 |
| 0078WP | 16 | GA | | | 9-0 | 33-23-24 | D06080 | 8 | | | SM00078 | 9 | | | 115-199 |
| 0079AJ | 20 | GA | | | 8-10 | 35-21-22 | D06080 | 11 | | | SM00079 | 9 | | | 001-099 |
| 0079AJ | 20 | GA | | | 9-0 | 35-21-22 | D06080 | 11 | | | SM00079 | 9 | | | 115-199 |
| 0080K | 18 | GA | | | 8-10 | 35-21-22 | D06080 | 10 | | | SM00080 | 9 | | | 001-099 |
| 0080K | 18 | GA | | | 9-0 | 35-21-22 | D06080 | 10 | | | SM00080 | 9 | | | 115-199 |
| 0081G | 16 | GA | | | 12-7 | 33-24-23 | D06082 | 1 | | | SM00071 | 9 | | | 001-099 |
| 0081G | 16 | GA | | | 13-0 | 33-24-23 | D06082 | 1 | | | SM00071 | 9 | | | 115-199 |
| 0082WV | 22 | GA | | | 12-7 | 33-25-24 | D06082 | 2 | | | SM00072 | 9 | | | 001-099 |
| 0082WV | 22 | GA | | | 13-0 | 33-25-24 | D06082 | 2 | | | SM00072 | 9 | | | 115-199 |
| 0083WG | 22 | GA | | | 12-7 | 33-25-24 | D06082 | 3 | | | SM00073 | 9 | | | 001-099 |
| 0083WG | 22 | GA | | | 13-0 | 33-25-24 | D06082 | 3 | | | SM00073 | 9 | | | 115-199 |
| 0085V | 22 | GA | | | 12-7 | 33-25-24 | D06082 | 5 | | | SM00075 | 9 | | | 001-099 |
| 0085V | 22 | GA | | | 13-0 | 33-25-24 | D06082 | 5 | | | SM00075 | 9 | | | 115-199 |
| 0086WN | 16 | GA | | | 12-7 | 33-23-24 | D06082 | 6 | | | SM00076 | 9 | | | 001-099 |
| 0086WN | 16 | GA | | | 13-0 | 33-23-24 | D06082 | 6 | | | SM00076 | 9 | | | 115-199 |
| 0087W | 20 | GA | | | 12-7 | 33-24-23 | D06082 | 7 | | | SM00077 | 9 | | | 001-099 |
| 0087W | 20 | GA | | | 13-0 | 33-24-23 | D06082 | 7 | | | SM00077 | 9 | | | 115-199 |
| 0088WP | 16 | GA | | | 12-7 | 33-23-24 | D06082 | 8 | | | SM00078 | 9 | | | 001-099 |
| 0088WP | 16 | GA | | | 13-0 | 33-23-24 | D06082 | 8 | | | SM00078 | 9 | | | 115-199 |
| 0089AJ | 20 | GA | | | 12-7 | 35-21-22 | D06082 | 11 | | | SM00079 | 9 | | | 001-099 |
| 0089AJ | 20 | GA | | | 13-0 | 35-21-22 | D06082 | 11 | | | SM00079 | 9 | | | 115-199 |
| 0090K | 18 | GA | | | 12-7 | 35-21-22 | D06082 | 10 | | | SM00080 | 9 | | | 001-099 |
| 0090K | 18 | GA | | | 13-0 | 35-21-22 | D06082 | 10 | | | SM00080 | 9 | | | 115-199 |
| 0091G | 16 | GA | | | 9-4 | 33-24-23 | D06084 | 1 | | | SM00091 | 9 | | | 001-099 |
| 0091G | 16 | GA | | | 9-0 | 33-24-23 | D06084 | 1 | | | SM00091 | 9 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 32

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | 286N3806 | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | |
| 0092WV | 22 | | GA | | 9-4 | 33-25-24 | D06084 | | 2 | | SM00092 | | 9 | | 001-099 |
| 0092WV | 22 | | GA | | 9-0 | 33-25-24 | D06084 | | 2 | | SM00092 | | 9 | | 115-199 |
| 0093WG | 22 | | GA | | 9-4 | 33-25-24 | D06084 | | 3 | | SM00093 | | 9 | | 001-099 |
| 0093WG | 22 | | GA | | 9-0 | 33-25-24 | D06084 | | 3 | | SM00093 | | 9 | | 115-199 |
| 0095V | 22 | | GA | | 9-4 | 33-25-24 | D06084 | | 5 | | SM00095 | | 9 | | 001-099 |
| 0095V | 22 | | GA | | 9-0 | 33-25-24 | D06084 | | 5 | | SM00095 | | 9 | | 115-199 |
| 0096WN | 16 | | GA | | 9-4 | 33-23-24 | D06084 | | 6 | | SM00096 | | 9 | | 001-099 |
| 0096WN | 16 | | GA | | 9-0 | 33-23-24 | D06084 | | 6 | | SM00096 | | 9 | | 115-199 |
| 0097W | 20 | | GA | | 9-4 | 33-24-23 | D06084 | | 7 | | SM00097 | | 9 | | 001-099 |
| 0097W | 20 | | GA | | 9-0 | 33-24-23 | D06084 | | 7 | | SM00097 | | 9 | | 115-199 |
| 0098WP | 16 | | GA | | 9-4 | 33-23-24 | D06084 | | 8 | | SM00098 | | 9 | | 001-099 |
| 0098WP | 16 | | GA | | 9-0 | 33-23-24 | D06084 | | 8 | | SM00098 | | 9 | | 115-199 |
| 0099AJ | 20 | | GA | | 9-4 | 35-21-22 | D06084 | | 11 | | SM00099 | | 9 | | 001-099 |
| 0099AJ | 20 | | GA | | 9-0 | 35-21-22 | D06084 | | 11 | | SM00099 | | 9 | | 115-199 |
| 0100K | 18 | | GA | | 9-4 | 35-21-22 | D06084 | | 10 | | SM00100 | | 9 | | 001-099 |
| 0100K | 18 | | GA | | 9-0 | 35-21-22 | D06084 | | 10 | | SM00100 | | 9 | | 115-199 |
| 0101G | 16 | | GA | | 10-8 | 33-24-23 | D06086 | | 1 | | SM00091 | | 9 | | 001-099 |
| 0101G | 16 | | GA | | 11-0 | 33-24-23 | D06086 | | 1 | | SM00091 | | 9 | | 115-199 |
| 0102WV | 22 | | GA | | 10-8 | 33-25-24 | D06086 | | 2 | | SM00092 | | 9 | | 001-099 |
| 0102WV | 22 | | GA | | 11-0 | 33-25-24 | D06086 | | 2 | | SM00092 | | 9 | | 115-199 |
| 0103WG | 22 | | GA | | 10-8 | 33-25-24 | D06086 | | 3 | | SM00093 | | 9 | | 001-099 |
| 0103WG | 22 | | GA | | 11-0 | 33-25-24 | D06086 | | 3 | | SM00093 | | 9 | | 115-199 |
| 0105V | 22 | | GA | | 10-8 | 33-25-24 | D06086 | | 5 | | SM00095 | | 9 | | 001-099 |
| 0105V | 22 | | GA | | 11-0 | 33-25-24 | D06086 | | 5 | | SM00095 | | 9 | | 115-199 |
| 0106WN | 16 | | GA | | 10-8 | 33-23-24 | D06086 | | 6 | | SM00096 | | 9 | | 001-099 |
| 0106WN | 16 | | GA | | 11-0 | 33-23-24 | D06086 | | 6 | | SM00096 | | 9 | | 115-199 |
| 0107W | 20 | | GA | | 10-8 | 33-24-23 | D06086 | | 7 | | SM00097 | | 9 | | 001-099 |
| 0107W | 20 | | GA | | 11-0 | 33-24-23 | D06086 | | 7 | | SM00097 | | 9 | | 115-199 |
| 0108WP | 16 | | GA | | 10-8 | 33-23-24 | D06086 | | 8 | | SM00098 | | 9 | | 001-099 |
| 0108WP | 16 | | GA | | 11-0 | 33-23-24 | D06086 | | 8 | | SM00098 | | 9 | | 115-199 |
| 0109AJ | 20 | | GA | | 10-8 | 35-21-22 | D06086 | | 11 | | SM00099 | | 9 | | 001-099 |
| 0109AJ | 20 | | GA | | 11-0 | 35-21-22 | D06086 | | 11 | | SM00099 | | 9 | | 115-199 |
| 0110K | 18 | | GA | | 10-8 | 35-21-22 | D06086 | | 10 | | SM00100 | | 9 | | 001-099 |
| 0110K | 18 | | GA | | 11-0 | 35-21-22 | D06086 | | 10 | | SM00100 | | 9 | | 115-199 |
| 0111G | 16 | | GA | | 8-1 | 33-24-23 | D06088 | | 1 | | SM00111 | | 9 | | 001-099 |
| 0111G | 16 | | GA | | 9-0 | 33-24-23 | D06088 | | 1 | | SM00111 | | 9 | | 115-199 |
| 0112WV | 22 | | GA | | 8-1 | 33-25-24 | D06088 | | 2 | | SM00112 | | 9 | | 001-099 |
| 0112WV | 22 | | GA | | 9-0 | 33-25-24 | D06088 | | 2 | | SM00112 | | 9 | | 115-199 |
| 0113WG | 22 | | GA | | 8-1 | 33-25-24 | D06088 | | 3 | | SM00113 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 33

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------------------|----------|--------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W3806 | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | | |
| 0113WG | 22 | | GA | | 9-0 | 33-25-24 | D06088 | | | 3 | | | SM00113 | | 9 | | 115-199 |
| 0115V | 22 | | GA | | 8-1 | 33-25-24 | D06088 | | | 5 | | | SM00115 | | 9 | | 001-099 |
| 0115V | 22 | | GA | | 9-0 | 33-25-24 | D06088 | | | 5 | | | SM00115 | | 9 | | 115-199 |
| 0116WN | 16 | | GA | | 8-1 | 33-23-24 | D06088 | | | 6 | | | SM00116 | | 9 | | 001-099 |
| 0116WN | 16 | | GA | | 9-0 | 33-23-24 | D06088 | | | 6 | | | SM00116 | | 9 | | 115-199 |
| 0117W | 20 | | GA | | 8-1 | 33-24-23 | D06088 | | | 7 | | | SM00117 | | 9 | | 001-099 |
| 0117W | 20 | | GA | | 9-0 | 33-24-23 | D06088 | | | 7 | | | SM00117 | | 9 | | 115-199 |
| 0118WP | 16 | | GA | | 8-1 | 33-23-24 | D06088 | | | 8 | | | SM00118 | | 9 | | 001-099 |
| 0118WP | 16 | | GA | | 9-0 | 33-23-24 | D06088 | | | 8 | | | SM00118 | | 9 | | 115-199 |
| 0119AJ | 20 | | GA | | 8-1 | 35-21-22 | D06088 | | | 11 | | | SM00119 | | 9 | | 001-099 |
| 0119AJ | 20 | | GA | | 9-0 | 35-21-22 | D06088 | | | 11 | | | SM00119 | | 9 | | 115-199 |
| 0120K | 18 | | GA | | 8-1 | 35-21-22 | D06088 | | | 10 | | | SM00120 | | 9 | | 001-099 |
| 0120K | 18 | | GA | | 9-0 | 35-21-22 | D06088 | | | 10 | | | SM00120 | | 9 | | 115-199 |
| 0121G | 16 | | GA | | 11-5 | 33-24-23 | D06090 | | | 1 | | | SM00111 | | 9 | | 001-099 |
| 0121G | 16 | | GA | | 12-0 | 33-24-23 | D06090 | | | 1 | | | SM00111 | | 9 | | 115-199 |
| 0122WV | 22 | | GA | | 11-5 | 33-25-24 | D06090 | | | 2 | | | SM00112 | | 9 | | 001-099 |
| 0122WV | 22 | | GA | | 12-0 | 33-25-24 | D06090 | | | 2 | | | SM00112 | | 9 | | 115-199 |
| 0123WG | 22 | | GA | | 11-5 | 33-25-24 | D06090 | | | 3 | | | SM00113 | | 9 | | 001-099 |
| 0123WG | 22 | | GA | | 12-0 | 33-25-24 | D06090 | | | 3 | | | SM00113 | | 9 | | 115-199 |
| 0125V | 22 | | GA | | 11-5 | 33-25-24 | D06090 | | | 5 | | | SM00115 | | 9 | | 001-099 |
| 0125V | 22 | | GA | | 12-0 | 33-25-24 | D06090 | | | 5 | | | SM00115 | | 9 | | 115-199 |
| 0126WN | 16 | | GA | | 11-5 | 33-23-24 | D06090 | | | 6 | | | SM00116 | | 9 | | 001-099 |
| 0126WN | 16 | | GA | | 12-0 | 33-23-24 | D06090 | | | 6 | | | SM00116 | | 9 | | 115-199 |
| 0127W | 20 | | GA | | 11-5 | 33-24-23 | D06090 | | | 7 | | | SM00117 | | 9 | | 001-099 |
| 0127W | 20 | | GA | | 12-0 | 33-24-23 | D06090 | | | 7 | | | SM00117 | | 9 | | 115-199 |
| 0128WP | 16 | | GA | | 11-5 | 33-23-24 | D06090 | | | 8 | | | SM00118 | | 9 | | 001-099 |
| 0128WP | 16 | | GA | | 12-0 | 33-23-24 | D06090 | | | 8 | | | SM00118 | | 9 | | 115-199 |
| 0129AJ | 20 | | GA | | 11-5 | 35-21-22 | D06090 | | | 11 | | | SM00119 | | 9 | | 001-099 |
| 0129AJ | 20 | | GA | | 12-0 | 35-21-22 | D06090 | | | 11 | | | SM00119 | | 9 | | 115-199 |
| 0130K | 18 | | GA | | 11-5 | 35-21-22 | D06090 | | | 10 | | | SM00120 | | 9 | | 001-099 |
| 0130K | 18 | | GA | | 12-0 | 35-21-22 | D06090 | | | 10 | | | SM00120 | | 9 | | 115-199 |
| 0131G | 16 | | GA | | 7-3 | 33-24-23 | D06092 | | | 1 | | | SM00131 | | 9 | | 001-099 |
| 0131G | 16 | | GA | | 8-0 | 33-24-23 | D06092 | | | 1 | | | SM00131 | | 9 | | 115-199 |
| 0132WV | 22 | | GA | | 7-3 | 33-25-24 | D06092 | | | 2 | | | SM00132 | | 9 | | 001-099 |
| 0132WV | 22 | | GA | | 8-0 | 33-25-24 | D06092 | | | 2 | | | SM00132 | | 9 | | 115-199 |
| 0133WG | 22 | | GA | | 7-3 | 33-25-24 | D06092 | | | 3 | | | SM00133 | | 9 | | 001-099 |
| 0133WG | 22 | | GA | | 8-0 | 33-25-24 | D06092 | | | 3 | | | SM00133 | | 9 | | 115-199 |
| 0135V | 22 | | GA | | 7-3 | 33-25-24 | D06092 | | | 5 | | | SM00135 | | 9 | | 001-099 |
| 0135V | 22 | | GA | | 8-0 | 33-25-24 | D06092 | | | 5 | | | SM00135 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 34

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | |
| 0136WN | 16 | | GA | | 7-3 | 33-23-24 | | D06092 | | | | SM00136 | | 9 | | 001-099 |
| 0136WN | 16 | | GA | | 8-0 | 33-23-24 | | D06092 | | | | SM00136 | | 9 | | 115-199 |
| 0137W | 20 | | GA | | 7-3 | 33-24-23 | | D06092 | | | | SM00137 | | 9 | | 001-099 |
| 0137W | 20 | | GA | | 8-0 | 33-24-23 | | D06092 | | | | SM00137 | | 9 | | 115-199 |
| 0138WP | 16 | | GA | | 7-3 | 33-23-24 | | D06092 | | | | SM00138 | | 9 | | 001-099 |
| 0138WP | 16 | | GA | | 8-0 | 33-23-24 | | D06092 | | | | SM00138 | | 9 | | 115-199 |
| 0139AJ | 20 | | GA | | 7-3 | 35-21-22 | | D06092 | | | 11 | SM00139 | | 9 | | 001-099 |
| 0139AJ | 20 | | GA | | 8-0 | 35-21-22 | | D06092 | | | 11 | SM00139 | | 9 | | 115-199 |
| 0140K | 18 | | GA | | 7-3 | 35-21-22 | | D06092 | | | 10 | SM00140 | | 9 | | 001-099 |
| 0140K | 18 | | GA | | 8-0 | 35-21-22 | | D06092 | | | 10 | SM00140 | | 9 | | 115-199 |
| 0141G | 16 | | GA | | 10-9 | 33-24-23 | | D06094 | | | 1 | SM00131 | | 9 | | 001-099 |
| 0141G | 16 | | GA | | 11-0 | 33-24-23 | | D06094 | | | 1 | SM00131 | | 9 | | 115-199 |
| 0142WV | 22 | | GA | | 10-9 | 33-25-24 | | D06094 | | | 2 | SM00132 | | 9 | | 001-099 |
| 0142WV | 22 | | GA | | 11-0 | 33-25-24 | | D06094 | | | 2 | SM00132 | | 9 | | 115-199 |
| 0143WG | 22 | | GA | | 10-9 | 33-25-24 | | D06094 | | | 3 | SM00133 | | 9 | | 001-099 |
| 0143WG | 22 | | GA | | 11-0 | 33-25-24 | | D06094 | | | 3 | SM00133 | | 9 | | 115-199 |
| 0145V | 22 | | GA | | 10-9 | 33-25-24 | | D06094 | | | 5 | SM00135 | | 9 | | 001-099 |
| 0145V | 22 | | GA | | 11-0 | 33-25-24 | | D06094 | | | 5 | SM00135 | | 9 | | 115-199 |
| 0146WN | 16 | | GA | | 10-9 | 33-23-24 | | D06094 | | | 6 | SM00136 | | 9 | | 001-099 |
| 0146WN | 16 | | GA | | 11-0 | 33-23-24 | | D06094 | | | 6 | SM00136 | | 9 | | 115-199 |
| 0147W | 20 | | GA | | 10-9 | 33-24-23 | | D06094 | | | 7 | SM00137 | | 9 | | 001-099 |
| 0147W | 20 | | GA | | 11-0 | 33-24-23 | | D06094 | | | 7 | SM00137 | | 9 | | 115-199 |
| 0148WP | 16 | | GA | | 10-9 | 33-23-24 | | D06094 | | | 8 | SM00138 | | 9 | | 001-099 |
| 0148WP | 16 | | GA | | 11-0 | 33-23-24 | | D06094 | | | 8 | SM00138 | | 9 | | 115-199 |
| 0149AJ | 20 | | GA | | 10-9 | 35-21-22 | | D06094 | | | 11 | SM00139 | | 9 | | 001-099 |
| 0149AJ | 20 | | GA | | 11-0 | 35-21-22 | | D06094 | | | 11 | SM00139 | | 9 | | 115-199 |
| 0150K | 18 | | GA | | 10-9 | 35-21-22 | | D06094 | | | 10 | SM00140 | | 9 | | 001-099 |
| 0150K | 18 | | GA | | 11-0 | 35-21-22 | | D06094 | | | 10 | SM00140 | | 9 | | 115-199 |
| 0151G | 16 | | GA | | 8-10 | 33-24-23 | | D06096 | | | 1 | SM00151 | | 9 | | 001-099 |
| 0151G | 16 | | GA | | 9-0 | 33-24-23 | | D06096 | | | 1 | SM00151 | | 9 | | 115-199 |
| 0152WV | 22 | | GA | | 8-10 | 33-25-24 | | D06096 | | | 2 | SM00152 | | 9 | | 001-099 |
| 0152WV | 22 | | GA | | 9-0 | 33-25-24 | | D06096 | | | 2 | SM00152 | | 9 | | 115-199 |
| 0153WG | 22 | | GA | | 8-10 | 33-25-24 | | D06096 | | | 3 | SM00153 | | 9 | | 001-099 |
| 0153WG | 22 | | GA | | 9-0 | 33-25-24 | | D06096 | | | 3 | SM00153 | | 9 | | 115-199 |
| 0155V | 22 | | GA | | 8-10 | 33-25-24 | | D06096 | | | 5 | SM00155 | | 9 | | 001-099 |
| 0155V | 22 | | GA | | 9-0 | 33-25-24 | | D06096 | | | 5 | SM00155 | | 9 | | 115-199 |
| 0156WN | 16 | | GA | | 8-10 | 33-23-24 | | D06096 | | | 6 | SM00156 | | 9 | | 001-099 |
| 0156WN | 16 | | GA | | 9-0 | 33-23-24 | | D06096 | | | 6 | SM00156 | | 9 | | 115-199 |
| 0157W | 20 | | GA | | 8-10 | 33-24-23 | | D06096 | | | 7 | SM00157 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 35

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|--------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | |
| 0157W | 20 | GA | | | 9-0 | 33-24-23 | D06096 | | | 7 | SM00157 | | | 9 | 115-199 |
| 0158WP | 16 | GA | | | 8-10 | 33-23-24 | D06096 | | | 8 | SM00158 | | | 9 | 001-099 |
| 0158WP | 16 | GA | | | 9-0 | 33-23-24 | D06096 | | | 8 | SM00158 | | | 9 | 115-199 |
| 0159AJ | 20 | GA | | | 8-10 | 35-21-22 | D06096 | | | 11 | SM00159 | | | 9 | 001-099 |
| 0159AJ | 20 | GA | | | 9-0 | 35-21-22 | D06096 | | | 11 | SM00159 | | | 9 | 115-199 |
| 0160K | 18 | GA | | | 8-10 | 35-21-22 | D06096 | | | 10 | SM00160 | | | 9 | 001-099 |
| 0160K | 18 | GA | | | 9-0 | 35-21-22 | D06096 | | | 10 | SM00160 | | | 9 | 115-199 |
| 0161G | 16 | GA | | | 7-10 | 33-24-23 | D06098 | | | 1 | SM00151 | | | 9 | 001-099 |
| 0161G | 16 | GA | | | 8-0 | 33-24-23 | D06098 | | | 1 | SM00151 | | | 9 | 115-199 |
| 0162WV | 22 | GA | | | 7-10 | 33-25-24 | D06098 | | | 2 | SM00152 | | | 9 | 001-099 |
| 0162WV | 22 | GA | | | 8-0 | 33-25-24 | D06098 | | | 2 | SM00152 | | | 9 | 115-199 |
| 0163WG | 22 | GA | | | 7-10 | 33-25-24 | D06098 | | | 3 | SM00153 | | | 9 | 001-099 |
| 0163WG | 22 | GA | | | 8-0 | 33-25-24 | D06098 | | | 3 | SM00153 | | | 9 | 115-199 |
| 0165V | 22 | GA | | | 7-10 | 33-25-24 | D06098 | | | 5 | SM00155 | | | 9 | 001-099 |
| 0165V | 22 | GA | | | 8-0 | 33-25-24 | D06098 | | | 5 | SM00155 | | | 9 | 115-199 |
| 0166WN | 16 | GA | | | 7-10 | 33-23-24 | D06098 | | | 6 | SM00156 | | | 9 | 001-099 |
| 0166WN | 16 | GA | | | 8-0 | 33-23-24 | D06098 | | | 6 | SM00156 | | | 9 | 115-199 |
| 0167W | 20 | GA | | | 7-10 | 33-24-23 | D06098 | | | 7 | SM00157 | | | 9 | 001-099 |
| 0167W | 20 | GA | | | 8-0 | 33-24-23 | D06098 | | | 7 | SM00157 | | | 9 | 115-199 |
| 0168WP | 16 | GA | | | 7-10 | 33-23-24 | D06098 | | | 8 | SM00158 | | | 9 | 001-099 |
| 0168WP | 16 | GA | | | 8-0 | 33-23-24 | D06098 | | | 8 | SM00158 | | | 9 | 115-199 |
| 0169AJ | 20 | GA | | | 7-10 | 35-21-22 | D06098 | | | 11 | SM00159 | | | 9 | 001-099 |
| 0169AJ | 20 | GA | | | 8-0 | 35-21-22 | D06098 | | | 11 | SM00159 | | | 9 | 115-199 |
| 0170K | 18 | GA | | | 7-10 | 35-21-22 | D06098 | | | 10 | SM00160 | | | 9 | 001-099 |
| 0170K | 18 | GA | | | 8-0 | 35-21-22 | D06098 | | | 10 | SM00160 | | | 9 | 115-199 |
| 0291G | 16 | GA | | | 8-6 | 33-24-23 | D07346 | | | 1 | SM00051 | | | 9 | 001-099 |
| 0291G | 16 | GA | | | 9-0 | 33-24-23 | D07346 | | | 1 | SM00051 | | | 9 | 115-199 |
| 0292WV | 22 | GA | | | 8-6 | 33-25-24 | D07346 | | | 2 | SM00052 | | | 9 | 001-099 |
| 0292WV | 22 | GA | | | 9-0 | 33-25-24 | D07346 | | | 2 | SM00052 | | | 9 | 115-199 |
| 0293WG | 22 | GA | | | 8-6 | 33-25-24 | D07346 | | | 3 | SM00053 | | | 9 | 001-099 |
| 0293WG | 22 | GA | | | 9-0 | 33-25-24 | D07346 | | | 3 | SM00053 | | | 9 | 115-199 |
| 0295V | 22 | GA | | | 8-6 | 33-25-24 | D07346 | | | 5 | SM00055 | | | 9 | 001-099 |
| 0295V | 22 | GA | | | 9-0 | 33-25-24 | D07346 | | | 5 | SM00055 | | | 9 | 115-199 |
| 0296WN | 16 | GA | | | 8-6 | 33-23-24 | D07346 | | | 6 | SM00056 | | | 9 | 001-099 |
| 0296WN | 16 | GA | | | 9-0 | 33-23-24 | D07346 | | | 6 | SM00056 | | | 9 | 115-199 |
| 0297W | 20 | GA | | | 8-6 | 33-24-23 | D07346 | | | 7 | SM00057 | | | 9 | 001-099 |
| 0297W | 20 | GA | | | 9-0 | 33-24-23 | D07346 | | | 7 | SM00057 | | | 9 | 115-199 |
| 0298WP | 16 | GA | | | 8-6 | 33-23-24 | D07346 | | | 8 | SM00058 | | | 9 | 001-099 |
| 0298WP | 16 | GA | | | 9-0 | 33-23-24 | D07346 | | | 8 | SM00058 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 36

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | |
| 0299AJ | 20 | | GA | | 8-6 | 35-21-22 | | D07346 | | 11 | | SM00059 | | 9 | | 001-099 |
| 0299AJ | 20 | | GA | | 9-0 | 35-21-22 | | D07346 | | 11 | | SM00059 | | 9 | | 115-199 |
| 0300K | 18 | | GA | | 8-6 | 35-21-22 | | D07346 | | 10 | | SM00060 | | 9 | | 001-099 |
| 0300K | 18 | | GA | | 9-0 | 35-21-22 | | D07346 | | 10 | | SM00060 | | 9 | | 115-199 |
| 0391G | 16 | | GA | | 11-7 | 33-24-23 | | D07012 | | 1 | | SM00031 | | 9 | | 001-099 |
| 0391G | 16 | | GA | | 13-0 | 33-24-23 | | D07012 | | 1 | | SM00031 | | 9 | | 115-199 |
| 0392WV | 22 | | GA | | 11-7 | 33-25-24 | | D07012 | | 2 | | SM00032 | | 9 | | 001-099 |
| 0392WV | 22 | | GA | | 13-0 | 33-25-24 | | D07012 | | 2 | | SM00032 | | 9 | | 115-199 |
| 0393WG | 22 | | GA | | 11-7 | 33-25-24 | | D07012 | | 3 | | SM00033 | | 9 | | 001-099 |
| 0393WG | 22 | | GA | | 13-0 | 33-25-24 | | D07012 | | 3 | | SM00033 | | 9 | | 115-199 |
| 0395V | 22 | | GA | | 11-7 | 33-25-24 | | D07012 | | 5 | | SM00035 | | 9 | | 001-099 |
| 0395V | 22 | | GA | | 13-0 | 33-25-24 | | D07012 | | 5 | | SM00035 | | 9 | | 115-199 |
| 0396WN | 16 | | GA | | 11-7 | 33-23-23 | | D07012 | | 6 | | SM00036 | | 9 | | 001-099 |
| 0396WN | 16 | | GA | | 13-0 | 33-23-23 | | D07012 | | 6 | | SM00036 | | 9 | | 115-199 |
| 0397W | 20 | | GA | | 11-7 | 33-24-23 | | D07012 | | 7 | | SM00037 | | 9 | | 001-099 |
| 0397W | 20 | | GA | | 13-0 | 33-24-23 | | D07012 | | 7 | | SM00037 | | 9 | | 115-199 |
| 0398WP | 16 | | GA | | 11-7 | 33-23-23 | | D07012 | | 8 | | SM00038 | | 9 | | 001-099 |
| 0398WP | 16 | | GA | | 13-0 | 33-23-23 | | D07012 | | 8 | | SM00038 | | 9 | | 115-199 |
| 0399AJ | 20 | | GA | | 11-7 | 35-21-22 | | D07012 | | 11 | | SM00039 | | 9 | | 001-099 |
| 0399AJ | 20 | | GA | | 13-0 | 35-21-22 | | D07012 | | 11 | | SM00039 | | 9 | | 115-199 |
| 0400K | 18 | | GA | | 11-7 | 35-21-22 | | D07012 | | 10 | | SM00040 | | 9 | | 001-099 |
| 0400K | 18 | | GA | | 13-0 | 35-21-22 | | D07012 | | 10 | | SM00040 | | 9 | | 115-199 |
| 0411G | 16 | | GA | | 3-10 | 33-24-23 | | SM00011 | | | 9 | SM00031 | | 9 | | 001-099 |
| 0411G | 16 | | GA | | 5-0 | 33-24-23 | | SM00011 | | | 9 | SM00031 | | 9 | | 115-199 |
| 0412WV | 22 | | GA | | 3-10 | 33-25-24 | | SM00012 | | | 9 | SM00032 | | 9 | | 001-099 |
| 0412WV | 22 | | GA | | 5-0 | 33-25-24 | | SM00012 | | | 9 | SM00032 | | 9 | | 115-199 |
| 0413WG | 22 | | GA | | 3-10 | 33-25-24 | | SM00013 | | | 9 | SM00033 | | 9 | | 001-099 |
| 0413WG | 22 | | GA | | 5-0 | 33-25-24 | | SM00013 | | | 9 | SM00033 | | 9 | | 115-199 |
| 0415V | 22 | | GA | | 3-10 | 33-25-24 | | SM00015 | | | 9 | SM00035 | | 9 | | 001-099 |
| 0415V | 22 | | GA | | 5-0 | 33-25-24 | | SM00015 | | | 9 | SM00035 | | 9 | | 115-199 |
| 0416WN | 16 | | GA | | 3-10 | 33-23-23 | | SM00016 | | | 9 | SM00036 | | 9 | | 001-099 |
| 0416WN | 16 | | GA | | 5-0 | 33-23-23 | | SM00016 | | | 9 | SM00036 | | 9 | | 115-199 |
| 0417W | 20 | | GA | | 3-10 | 33-24-23 | | SM00017 | | | 9 | SM00037 | | 9 | | 001-099 |
| 0417W | 20 | | GA | | 5-0 | 33-24-23 | | SM00017 | | | 9 | SM00037 | | 9 | | 115-199 |
| 0418WP | 16 | | GA | | 3-10 | 33-23-23 | | SM00018 | | | 9 | SM00038 | | 9 | | 001-099 |
| 0418WP | 16 | | GA | | 5-0 | 33-23-23 | | SM00018 | | | 9 | SM00038 | | 9 | | 115-199 |
| 0419AJ | 16 | | GA | | 3-10 | 35-21-22 | | SM00019 | | | 9 | SM00039 | | 9 | | 001-099 |
| 0419AJ | 16 | | GA | | 5-0 | 35-21-22 | | SM00019 | | | 9 | SM00039 | | 9 | | 115-199 |
| 0420K | 18 | | GA | | 3-10 | 35-21-22 | | SM00020 | | | 9 | SM00040 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 37

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | |
| 0420K | 18 | | GA | | 5-0 | 35-21-22 | SM00020 | | | 9 | SM00040 | | | 9 | 115-199 |
| 0431G | 16 | | GA | | 5-4 | 33-24-23 | SM00031 | | | 9 | SM00051 | | | 9 | 001-099 |
| 0431G | 16 | | GA | | 7-0 | 33-24-23 | SM00031 | | | 9 | SM00051 | | | 9 | 115-199 |
| 0432WV | 22 | | GA | | 5-4 | 33-25-24 | SM00032 | | | 9 | SM00052 | | | 9 | 001-099 |
| 0432WV | 22 | | GA | | 7-0 | 33-25-24 | SM00032 | | | 9 | SM00052 | | | 9 | 115-199 |
| 0435V | 22 | | GA | | 5-4 | 33-25-24 | SM00035 | | | 9 | SM00055 | | | 9 | 001-099 |
| 0435V | 22 | | GA | | 7-0 | 33-25-24 | SM00035 | | | 9 | SM00055 | | | 9 | 115-199 |
| 0437W | 20 | | GA | | 5-4 | 33-24-23 | SM00037 | | | 9 | SM00057 | | | 9 | 001-099 |
| 0437W | 20 | | GA | | 7-0 | 33-24-23 | SM00037 | | | 9 | SM00057 | | | 9 | 115-199 |
| 0438WP | 16 | | GA | | 5-4 | 33-23-23 | SM00038 | | | 9 | SM00058 | | | 9 | 001-099 |
| 0438WP | 16 | | GA | | 7-0 | 33-23-23 | SM00038 | | | 9 | SM00058 | | | 9 | 115-199 |
| 0439AJ | 16 | | GA | | 5-4 | 35-21-22 | SM00039 | | | 9 | SM00059 | | | 9 | 001-099 |
| 0439AJ | 16 | | GA | | 7-0 | 35-21-22 | SM00039 | | | 9 | SM00059 | | | 9 | 115-199 |
| 0440K | 18 | | GA | | 5-4 | 35-21-22 | SM00040 | | | 9 | SM00060 | | | 9 | 001-099 |
| 0440K | 18 | | GA | | 7-0 | 35-21-22 | SM00040 | | | 9 | SM00060 | | | 9 | 115-199 |
| 0451G | 16 | | GA | | 4-1 | 33-24-23 | SM00051 | | | 9 | SM00071 | | | 9 | 001-099 |
| 0451G | 16 | | GA | | 5-0 | 33-24-23 | SM00051 | | | 9 | SM00071 | | | 9 | 115-199 |
| 0452WV | 22 | | GA | | 4-1 | 33-25-24 | SM00052 | | | 9 | SM00072 | | | 9 | 001-099 |
| 0452WV | 22 | | GA | | 5-0 | 33-25-24 | SM00052 | | | 9 | SM00072 | | | 9 | 115-199 |
| 0453WG | 22 | | GA | | 4-1 | 33-25-24 | SM00053 | | | 9 | SM00073 | | | 9 | 001-099 |
| 0453WG | 22 | | GA | | 5-0 | 33-25-24 | SM00053 | | | 9 | SM00073 | | | 9 | 115-199 |
| 0455V | 22 | | GA | | 4-1 | 33-25-24 | SM00055 | | | 9 | SM00075 | | | 9 | 001-099 |
| 0455V | 22 | | GA | | 5-0 | 33-25-24 | SM00055 | | | 9 | SM00075 | | | 9 | 115-199 |
| 0456WN | 16 | | GA | | 4-1 | 33-23-24 | SM00056 | | | 9 | SM00076 | | | 9 | 001-099 |
| 0456WN | 16 | | GA | | 5-0 | 33-23-24 | SM00056 | | | 9 | SM00076 | | | 9 | 115-199 |
| 0457W | 20 | | GA | | 4-1 | 33-24-23 | SM00057 | | | 9 | SM00077 | | | 9 | 001-099 |
| 0457W | 20 | | GA | | 5-0 | 33-24-23 | SM00057 | | | 9 | SM00077 | | | 9 | 115-199 |
| 0458WP | 16 | | GA | | 4-1 | 33-23-24 | SM00058 | | | 9 | SM00078 | | | 9 | 001-099 |
| 0458WP | 16 | | GA | | 5-0 | 33-23-24 | SM00058 | | | 9 | SM00078 | | | 9 | 115-199 |
| 0459AJ | 16 | | GA | | 4-1 | 35-21-22 | SM00059 | | | 9 | SM00079 | | | 9 | 001-099 |
| 0459AJ | 16 | | GA | | 5-0 | 35-21-22 | SM00059 | | | 9 | SM00079 | | | 9 | 115-199 |
| 0460K | 18 | | GA | | 4-1 | 35-21-22 | SM00060 | | | 9 | SM00080 | | | 9 | 001-099 |
| 0460K | 18 | | GA | | 5-0 | 35-21-22 | SM00060 | | | 9 | SM00080 | | | 9 | 115-199 |
| 0471G | 16 | | GA | | 6-2 | 33-24-23 | SM00071 | | | 9 | SM00091 | | | 9 | 001-099 |
| 0471G | 16 | | GA | | 7-0 | 33-24-23 | SM00071 | | | 9 | SM00091 | | | 9 | 115-199 |
| 0472WV | 22 | | GA | | 6-2 | 33-25-24 | SM00072 | | | 9 | SM00092 | | | 9 | 001-099 |
| 0472WV | 22 | | GA | | 7-0 | 33-25-24 | SM00072 | | | 9 | SM00092 | | | 9 | 115-199 |
| 0473WG | 22 | | GA | | 6-2 | 33-25-24 | SM00073 | | | 9 | SM00093 | | | 9 | 001-099 |
| 0473WG | 22 | | GA | | 7-0 | 33-25-24 | SM00073 | | | 9 | SM00093 | | | 9 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 38

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | |
| 0475V | 22 | | GA | | 6-2 | 33-25-24 | | SM00075 | | | | SM00095 | | | | 001-099 |
| 0475V | 22 | | GA | | 7-0 | 33-25-24 | | SM00075 | | | | SM00095 | | | | 115-199 |
| 0476WN | 16 | | GA | | 6-2 | 33-23-24 | | SM00076 | | | | SM00096 | | | | 001-099 |
| 0476WN | 16 | | GA | | 7-0 | 33-23-24 | | SM00076 | | | | SM00096 | | | | 115-199 |
| 0477W | 20 | | GA | | 6-2 | 33-24-23 | | SM00077 | | | | SM00097 | | | | 001-099 |
| 0477W | 20 | | GA | | 7-0 | 33-24-23 | | SM00077 | | | | SM00097 | | | | 115-199 |
| 0478WP | 16 | | GA | | 6-2 | 33-23-24 | | SM00078 | | | | SM00098 | | | | 001-099 |
| 0478WP | 16 | | GA | | 7-0 | 33-23-24 | | SM00078 | | | | SM00098 | | | | 115-199 |
| 0479AJ | 16 | | GA | | 6-2 | 35-21-22 | | SM00079 | | | | SM00099 | | | | 001-099 |
| 0479AJ | 16 | | GA | | 7-0 | 35-21-22 | | SM00079 | | | | SM00099 | | | | 115-199 |
| 0480K | 18 | | GA | | 6-2 | 35-21-22 | | SM00080 | | | | SM00100 | | | | 001-099 |
| 0480K | 18 | | GA | | 7-0 | 35-21-22 | | SM00080 | | | | SM00100 | | | | 115-199 |
| 0491G | 16 | | GA | | 6-3 | 33-24-23 | | SM00091 | | | | SM00111 | | | | 001-099 |
| 0491G | 16 | | GA | | 7-0 | 33-24-23 | | SM00091 | | | | SM00111 | | | | 115-199 |
| 0492WV | 22 | | GA | | 6-3 | 33-25-24 | | SM00092 | | | | SM00112 | | | | 001-099 |
| 0492WV | 22 | | GA | | 7-0 | 33-25-24 | | SM00092 | | | | SM00112 | | | | 115-199 |
| 0493WG | 22 | | GA | | 6-3 | 33-25-24 | | SM00093 | | | | SM00113 | | | | 001-099 |
| 0493WG | 22 | | GA | | 7-0 | 33-25-24 | | SM00093 | | | | SM00113 | | | | 115-199 |
| 0495V | 22 | | GA | | 6-3 | 33-25-24 | | SM00095 | | | | SM00115 | | | | 001-099 |
| 0495V | 22 | | GA | | 7-0 | 33-25-24 | | SM00095 | | | | SM00115 | | | | 115-199 |
| 0496WN | 16 | | GA | | 6-3 | 33-23-24 | | SM00096 | | | | SM00116 | | | | 001-099 |
| 0496WN | 16 | | GA | | 7-0 | 33-23-24 | | SM00096 | | | | SM00116 | | | | 115-199 |
| 0497W | 20 | | GA | | 6-3 | 33-24-23 | | SM00097 | | | | SM00117 | | | | 001-099 |
| 0497W | 20 | | GA | | 7-0 | 33-24-23 | | SM00097 | | | | SM00117 | | | | 115-199 |
| 0498WP | 16 | | GA | | 6-3 | 33-23-24 | | SM00098 | | | | SM00118 | | | | 001-099 |
| 0498WP | 16 | | GA | | 7-0 | 33-23-24 | | SM00098 | | | | SM00118 | | | | 115-199 |
| 0499AJ | 16 | | GA | | 6-3 | 35-21-22 | | SM00099 | | | | SM00119 | | | | 001-099 |
| 0499AJ | 16 | | GA | | 7-0 | 35-21-22 | | SM00099 | | | | SM00119 | | | | 115-199 |
| 0500K | 18 | | GA | | 6-3 | 35-21-22 | | SM00100 | | | | SM00120 | | | | 001-099 |
| 0500K | 18 | | GA | | 7-0 | 35-21-22 | | SM00100 | | | | SM00120 | | | | 115-199 |
| 0511G | 16 | | GA | | 5-3 | 33-24-23 | | SM00111 | | | | SM00131 | | | | 001-099 |
| 0511G | 16 | | GA | | 7-0 | 33-24-23 | | SM00111 | | | | SM00131 | | | | 115-199 |
| 0512WV | 22 | | GA | | 5-3 | 33-25-24 | | SM00112 | | | | SM00132 | | | | 001-099 |
| 0512WV | 22 | | GA | | 7-0 | 33-25-24 | | SM00112 | | | | SM00132 | | | | 115-199 |
| 0513WG | 22 | | GA | | 5-3 | 33-25-24 | | SM00113 | | | | SM00133 | | | | 001-099 |
| 0513WG | 22 | | GA | | 7-0 | 33-25-24 | | SM00113 | | | | SM00133 | | | | 115-199 |
| 0515V | 22 | | GA | | 5-3 | 33-25-24 | | SM00115 | | | | SM00135 | | | | 001-099 |
| 0515V | 22 | | GA | | 7-0 | 33-25-24 | | SM00115 | | | | SM00135 | | | | 115-199 |
| 0516WN | 16 | | GA | | 5-3 | 33-23-24 | | SM00116 | | | | SM00136 | | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 39

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | 286N3806 | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | |
| 0516WN | 16 | GA | | | 7-0 | 33-23-24 | SM00116 | | 9 | | SM00136 | | 9 | | 115-199 |
| 0517W | 20 | GA | | | 5-3 | 33-24-23 | SM00117 | | 9 | | SM00137 | | 9 | | 001-099 |
| 0517W | 20 | GA | | | 7-0 | 33-24-23 | SM00117 | | 9 | | SM00137 | | 9 | | 115-199 |
| 0518WP | 16 | GA | | | 5-3 | 33-23-24 | SM00118 | | 9 | | SM00138 | | 9 | | 001-099 |
| 0518WP | 16 | GA | | | 7-0 | 33-23-24 | SM00118 | | 9 | | SM00138 | | 9 | | 115-199 |
| 0519AJ | 16 | GA | | | 5-3 | 35-21-22 | SM00119 | | 9 | | SM00139 | | 9 | | 001-099 |
| 0519AJ | 16 | GA | | | 7-0 | 35-21-22 | SM00119 | | 9 | | SM00139 | | 9 | | 115-199 |
| 0520K | 18 | GA | | | 5-3 | 35-21-22 | SM00120 | | 9 | | SM00140 | | 9 | | 001-099 |
| 0520K | 18 | GA | | | 7-0 | 35-21-22 | SM00120 | | 9 | | SM00140 | | 9 | | 115-199 |
| 0531G | 16 | GA | | | 3-11 | 33-24-23 | SM00131 | | 9 | | SM00151 | | 9 | | 001-099 |
| 0531G | 16 | GA | | | 5-0 | 33-24-23 | SM00131 | | 9 | | SM00151 | | 9 | | 115-199 |
| 0532WV | 22 | GA | | | 3-11 | 33-25-24 | SM00132 | | 9 | | SM00152 | | 9 | | 001-099 |
| 0532WV | 22 | GA | | | 5-0 | 33-25-24 | SM00132 | | 9 | | SM00152 | | 9 | | 115-199 |
| 0533WG | 22 | GA | | | 3-11 | 33-25-24 | SM00133 | | 9 | | SM00153 | | 9 | | 001-099 |
| 0533WG | 22 | GA | | | 5-0 | 33-25-24 | SM00133 | | 9 | | SM00153 | | 9 | | 115-199 |
| 0535V | 22 | GA | | | 3-11 | 33-25-24 | SM00135 | | 9 | | SM00155 | | 9 | | 001-099 |
| 0535V | 22 | GA | | | 5-0 | 33-25-24 | SM00135 | | 9 | | SM00155 | | 9 | | 115-199 |
| 0536WN | 16 | GA | | | 3-11 | 33-23-24 | SM00136 | | 9 | | SM00156 | | 9 | | 001-099 |
| 0536WN | 16 | GA | | | 5-0 | 33-23-24 | SM00136 | | 9 | | SM00156 | | 9 | | 115-199 |
| 0537W | 20 | GA | | | 3-11 | 33-24-23 | SM00137 | | 9 | | SM00157 | | 9 | | 001-099 |
| 0537W | 20 | GA | | | 5-0 | 33-24-23 | SM00137 | | 9 | | SM00157 | | 9 | | 115-199 |
| 0538WP | 16 | GA | | | 3-11 | 33-23-24 | SM00138 | | 9 | | SM00158 | | 9 | | 001-099 |
| 0538WP | 16 | GA | | | 5-0 | 33-23-24 | SM00138 | | 9 | | SM00158 | | 9 | | 115-199 |
| 0539AJ | 16 | GA | | | 3-11 | 35-21-22 | SM00139 | | 9 | | SM00159 | | 9 | | 001-099 |
| 0539AJ | 16 | GA | | | 5-0 | 35-21-22 | SM00139 | | 9 | | SM00159 | | 9 | | 115-199 |
| 0540K | 18 | GA | | | 3-11 | 35-21-22 | SM00140 | | 9 | | SM00160 | | 9 | | 001-099 |
| 0540K | 18 | GA | | | 5-0 | 35-21-22 | SM00140 | | 9 | | SM00160 | | 9 | | 115-199 |
| 0800 | 22 | GA | | | 13-0 | 23-31-41 | D06078 | 12 | | | SM00001 | | 9 | | 001-099 |
| 0800 | 22 | GA | | | 14-0 | 23-31-41 | SM00001 | | 9 | | D06078 | 15 | | | 115-199 |
| 0801 | 16 | GA | | | 2-7 | 33-24-23 | D40414P | 1 | | | SM00011 | 9 | | | 001-099 |
| 0801 | 16 | GA | | | 3-0 | 33-24-23 | D40414P | 1 | | | SM00011 | 9 | | | 115-199 |
| 0802 | 22 | GA | | | 2-7 | 33-25-24 | D40414P | 2 | | | SM00012 | 9 | | | 001-099 |
| 0802 | 22 | GA | | | 3-0 | 33-25-24 | D40414P | 2 | | | SM00012 | 9 | | | 115-199 |
| 0803 | 22 | GA | | | 2-7 | 33-25-24 | D40414P | 3 | | | SM00013 | 9 | | | 001-099 |
| 0803 | 22 | GA | | | 3-0 | 33-25-24 | D40414P | 3 | | | SM00013 | 9 | | | 115-199 |
| 0804 | 22 | GA | | | 9-9 | 23-31-41 | D07346 | 12 | | | SM00001 | 9 | | | 001-099 |
| 0804 | 22 | GA | | | 10-0 | 23-31-41 | SM00001 | | 9 | | D07346 | 15 | | | 115-199 |
| 0805 | 22 | GA | | | 2-7 | 33-25-24 | D40414P | 5 | | | SM00015 | 9 | | | 001-099 |
| 0805 | 22 | GA | | | 3-0 | 33-25-24 | D40414P | 5 | | | SM00015 | 9 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 40

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | 286N3806 | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | |
| 0806 | 16 | | GA | | 2-7 | 33-23-23 | D40414P | | 6 | | SM00016 | | 9 | | 001-099 |
| 0806 | 16 | | GA | | 3-0 | 33-23-23 | D40414P | | 6 | | SM00016 | | 9 | | 115-199 |
| 0807 | 20 | | GA | | 2-7 | 33-24-23 | D40414P | | 7 | | SM00017 | | 9 | | 001-099 |
| 0807 | 20 | | GA | | 3-0 | 33-24-23 | D40414P | | 7 | | SM00017 | | 9 | | 115-199 |
| 0808 | 16 | | GA | | 2-7 | 33-23-23 | D40414P | | 8 | | SM00018 | | 9 | | 001-099 |
| 0808 | 16 | | GA | | 3-0 | 33-23-23 | D40414P | | 8 | | SM00018 | | 9 | | 115-199 |
| 0809 | 16 | | GA | | 2-7 | 35-21-22 | D40414P | | 9 | | SM00019 | | 9 | | 001-099 |
| 0809 | 16 | | GA | | 3-0 | 35-21-22 | D40414P | | 9 | | SM00019 | | 9 | | 115-199 |
| 0810 | 18 | | GA | | 2-7 | 35-21-22 | D40414P | | 10 | | SM00020 | | 9 | | 001-099 |
| 0810 | 18 | | GA | | 3-0 | 35-21-22 | D40414P | | 10 | | SM00020 | | 9 | | 115-199 |
| 0816 | 22 | | GA | | 39-8 | SPARE | D01245 | | 3 | | D40414P | 19 | | | 001-099 |
| 0816 | 22 | | GA | | 40-0 | SPARE | D01245 | | 3 | | D40414P | 19 | | | 115-199 |
| 0823 | 14 | | GA | | 12-4 | 33-23-24 | T10018 | GND | E | | GD03171 | AC.. | E | | 001-099 |
| 0823 | 14 | | GA | | 13-0 | 33-23-24 | T10018 | GND | E | | GD03171 | AC.. | E | | 115-199 |
| 0826 | 16 | | GA | | 11-9 | 33-23-24 | T10018 | LV | E | | SM00076 | | 9 | | 001-099 |
| 0826 | 16 | | GA | | 12-0 | 33-23-24 | T10018 | LV | E | | SM00076 | | 9 | | 115-199 |
| 0828 | 20 | | GA | | 25-2 | 33-23-24 | D40414P | | 18 | | T10018 | HV3 | E | | 001-099 |
| 0828 | 20 | | GA | | 25-0 | 33-23-24 | D40414P | | 18 | | T10018 | HV3 | E | | 115-199 |
| 0835 | 22 | | GA | | 10-0 | 23-31-41 | D40414P | | 15 | | SM00001 | | 9 | | 001-099 |
| 0835 | 22 | | GA | | 11-0 | 23-31-41 | D40414P | | 15 | | SM00001 | | 9 | | 115-199 |
| 0918 | 16 | | GA | | 1-9 | 33-23-23 | SM00018 | | 9 | | GD03169 | AC.. | E | | 001-099 |
| 0918 | 16 | | GA | | 2-0 | 33-23-23 | SM00018 | | 9 | | GD03169 | AC.. | E | | 115-199 |
| 0920 | 18 | | GA | | 2-0 | 35-21-22 | SM00020 | | 9 | | GD03167 | DC.. | E | | ALL |
| 0921 | 16 | | GA | | 2-11 | 33-23-24 | SM00078 | | 9 | | GD03173 | AC.. | E | | 001-099 |
| 0921 | 16 | | GA | | 3-0 | 33-23-24 | SM00078 | | 9 | | GD03173 | AC.. | E | | 115-199 |
| 0922 | 16 | | GA | | 2-6 | 33-23-24 | SM00138 | | 9 | | GD03259 | AC.. | E | | 001-099 |
| 0922 | 16 | | GA | | 4-0 | 33-23-24 | SM00138 | | 9 | | GD03259 | AC.. | E | | 115-199 |
| 0923 | 16 | | GA | | 4-0 | 33-23-24 | SM00158 | | 9 | | GD03914 | AC.. | E | | ALL |
| 0938 | 16 | | GA | | 2-1 | 33-23-24 | SM00098 | | 9 | | GD03179 | AC.. | E | | ALL |
| 0940 | 18 | | GA | | 2-1 | 35-21-22 | SM00100 | | 9 | | GD03175 | DC.. | E | | ALL |
| 0942 | 18 | | GA | | 2-6 | 35-21-22 | SM00140 | | 9 | | GD03181 | DC.. | E | | 001-099 |
| 0942 | 18 | | GA | | 4-0 | 35-21-22 | SM00140 | | 9 | | GD03181 | DC.. | E | | 115-199 |
| 0944 | 22 | | GA | | 8-9 | 33-25-24 | SM00033 | | 9 | | SP00544 | | 9 | | 001-099 |
| 0948 | 22 | | GA | | 7-10 | 33-25-24 | SM00153 | | 9 | | SP00548 | | 9 | | 001-099 |
| 0948 | 22 | | GA | | 8-0 | 33-25-24 | SM00153 | | 9 | | SP00548 | | 9 | | 115-199 |
| 0951 | 20 | | GA | | 7-11 | 35-21-22 | D05238 | 1 | VY | | SM00159 | | 9 | | 001-099 |
| 0951 | 20 | | GA | | 8-0 | 35-21-22 | D05238 | 1 | VY | | SM00159 | | 9 | | 115-199 |
| 0952 | 18 | | GA | | 3-1 | 35-21-22 | D05240 | 1 | VG | | GD02603 | DC.. | E | | 001-099 |
| 0952 | 18 | | GA | | 4-0 | 35-21-22 | D05240 | 1 | VG | | GD02603 | DC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 41

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3806 | | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | |
| 0964 | 22 | GA | | | 8-0 | 33-25-24 | SM00152 | | 9 | | SP01130 | | 9 | | 115-199 |
| 0965 | 22 | GA | | | 10-0 | 33-25-24 | SM00032 | | 9 | | SP01594 | | 9 | | 115-199 |
| 0974 | 20 | GA | | | 7-6 | 23-31-32 | SM00160 | | 9 | | D01245 | 4 | | | 001-099 |
| 0974 | 20 | GA | | | 8-0 | 23-31-32 | SM00160 | | 9 | | D01245 | 4 | | | 115-199 |
| 2011B | 22 | GB | A | | 7-2 | 23-31-32 | D06068 | 14 | | | SM00024 | | 9 | | 001-099 |
| 2011B | 22 | GB | A | | 8-0 | 23-31-32 | D06068 | 13 | | | SM00023 | | 9 | | 115-199 |
| 2011R | 22 | GB | A | | 0-0 | 23-31-32 | D06068 | 13 | | | SM00023 | | 9 | | 001-099 |
| 2011R | 22 | GB | A | | 0-0 | 23-31-32 | D06068 | 14 | | | SM00024 | | 9 | | 115-199 |
| 2021B | 22 | GB | B | | 9-1 | 23-31-32 | D06070 | 14 | | | SM00024 | | 9 | | 001-099 |
| 2021B | 22 | GB | B | | 10-0 | 23-31-32 | D06070 | 13 | | | SM00023 | | 9 | | 115-199 |
| 2021R | 22 | GB | B | | 0-0 | 23-31-32 | D06070 | 13 | | | SM00023 | | 9 | | 001-099 |
| 2021R | 22 | GB | B | | 0-0 | 23-31-32 | D06070 | 14 | | | SM00024 | | 9 | | 115-199 |
| 2023B | 22 | GB | Q | | 3-10 | 23-31-32 | SM00024 | | 9 | | SM00044 | | 9 | | 001-099 |
| 2023B | 22 | GB | Q | | 5-0 | 23-31-32 | SM00023 | | 9 | | SM00043 | | 9 | | 115-199 |
| 2023R | 22 | GB | Q | | 0-0 | 23-31-32 | SM00023 | | 9 | | SM00043 | | 9 | | 001-099 |
| 2023R | 22 | GB | Q | | 0-0 | 23-31-32 | SM00024 | | 9 | | SM00044 | | 9 | | 115-199 |
| 2031B | 22 | GB | C | | 8-0 | 23-31-32 | D06072 | 14 | | | SM00044 | | 9 | | 001-099 |
| 2031B | 22 | GB | C | | 9-0 | 23-31-32 | D06072 | 13 | | | SM00043 | | 9 | | 115-199 |
| 2031R | 22 | GB | C | | 0-0 | 23-31-32 | D06072 | 13 | | | SM00043 | | 9 | | 001-099 |
| 2031R | 22 | GB | C | | 0-0 | 23-31-32 | D06072 | 14 | | | SM00044 | | 9 | | 115-199 |
| 2041B | 22 | GB | D | | 9-4 | 23-31-32 | D06074 | 14 | | | SM00044 | | 9 | | 001-099 |
| 2041B | 22 | GB | D | | 10-0 | 23-31-32 | D06074 | 13 | | | SM00043 | | 9 | | 115-199 |
| 2041R | 22 | GB | D | | 0-0 | 23-31-32 | D06074 | 13 | | | SM00043 | | 9 | | 001-099 |
| 2041R | 22 | GB | D | | 0-0 | 23-31-32 | D06074 | 14 | | | SM00044 | | 9 | | 115-199 |
| 2043B | 22 | GB | R | | 5-4 | 23-31-32 | SM00044 | | 9 | | SM00064 | | 9 | | 001-099 |
| 2043B | 22 | GB | R | | 7-0 | 23-31-32 | SM00043 | | 9 | | SM00063 | | 9 | | 115-199 |
| 2043R | 22 | GB | R | | 0-0 | 23-31-32 | SM00043 | | 9 | | SM00063 | | 9 | | 001-099 |
| 2043R | 22 | GB | R | | 0-0 | 23-31-32 | SM00044 | | 9 | | SM00064 | | 9 | | 115-199 |
| 2051B | 22 | GB | E | | 7-7 | 23-31-32 | D06076 | 14 | | | SM00064 | | 9 | | 001-099 |
| 2051B | 22 | GB | E | | 8-0 | 23-31-32 | D06076 | 13 | | | SM00063 | | 9 | | 115-199 |
| 2051R | 22 | GB | E | | 0-0 | 23-31-32 | D06076 | 13 | | | SM00063 | | 9 | | 001-099 |
| 2051R | 22 | GB | E | | 0-0 | 23-31-32 | D06076 | 14 | | | SM00064 | | 9 | | 115-199 |
| 2061B | 22 | GB | F | | 11-9 | 23-31-32 | D06078 | 14 | | | SM00064 | | 9 | | 001-099 |
| 2061B | 22 | GB | F | | 12-0 | 23-31-32 | D06078 | 13 | | | SM00063 | | 9 | | 115-199 |
| 2061R | 22 | GB | F | | 0-0 | 23-31-32 | D06078 | 13 | | | SM00063 | | 9 | | 001-099 |
| 2061R | 22 | GB | F | | 0-0 | 23-31-32 | D06078 | 14 | | | SM00064 | | 9 | | 115-199 |
| 2063B | 22 | GB | S | | 4-1 | 23-31-32 | SM00064 | | 9 | | SM00084 | | 9 | | 001-099 |
| 2063B | 22 | GB | S | | 5-0 | 23-31-32 | SM00063 | | 9 | | SM00083 | | 9 | | 115-199 |
| 2063R | 22 | GB | S | | 0-0 | 23-31-32 | SM00063 | | 9 | | SM00083 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 42

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W3806 | 286N3806 | | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | |
| 2063R | 22 | GB | S | | 0-0 | 23-31-32 | SM00064 | | | 9 | | SM00084 | | 9 | | 115-199 |
| 2071B | 22 | GB | G | | 8-10 | 23-31-32 | D06080 | | 14 | | | SM00084 | | 9 | | 001-099 |
| 2071B | 22 | GB | G | | 10-0 | 23-31-32 | D06080 | | 13 | | | SM00083 | | 9 | | 115-199 |
| 2071R | 22 | GB | G | | 0-0 | 23-31-32 | D06080 | | 13 | | | SM00083 | | 9 | | 001-099 |
| 2071R | 22 | GB | G | | 0-0 | 23-31-32 | D06080 | | 14 | | | SM00084 | | 9 | | 115-199 |
| 2081B | 22 | GB | H | | 12-7 | 23-31-32 | D06082 | | 14 | | | SM00084 | | 9 | | 001-099 |
| 2081B | 22 | GB | H | | 14-0 | 23-31-32 | D06082 | | 13 | | | SM00083 | | 9 | | 115-199 |
| 2081R | 22 | GB | H | | 0-0 | 23-31-32 | D06082 | | 13 | | | SM00083 | | 9 | | 001-099 |
| 2081R | 22 | GB | H | | 0-0 | 23-31-32 | D06082 | | 14 | | | SM00084 | | 9 | | 115-199 |
| 2083B | 22 | GB | T | | 6-2 | 23-31-32 | SM00084 | | | 9 | | SM00104 | | 9 | | 001-099 |
| 2083B | 22 | GB | T | | 7-0 | 23-31-32 | SM00083 | | | 9 | | SM00103 | | 9 | | 115-199 |
| 2083R | 22 | GB | T | | 0-0 | 23-31-32 | SM00083 | | | 9 | | SM00103 | | 9 | | 001-099 |
| 2083R | 22 | GB | T | | 0-0 | 23-31-32 | SM00084 | | | 9 | | SM00104 | | 9 | | 115-199 |
| 2091B | 22 | GB | I | | 9-4 | 23-31-32 | D06084 | | 14 | | | SM00104 | | 9 | | 001-099 |
| 2091B | 22 | GB | I | | 10-0 | 23-31-32 | D06084 | | 13 | | | SM00103 | | 9 | | 115-199 |
| 2091R | 22 | GB | I | | 0-0 | 23-31-32 | D06084 | | 13 | | | SM00103 | | 9 | | 001-099 |
| 2091R | 22 | GB | I | | 0-0 | 23-31-32 | D06084 | | 14 | | | SM00104 | | 9 | | 115-199 |
| 2101B | 22 | GB | J | | 10-8 | 23-31-32 | D06086 | | 14 | | | SM00104 | | 9 | | 001-099 |
| 2101B | 22 | GB | J | | 15-0 | 23-31-32 | D06086 | | 13 | | | SM00103 | | 9 | | 115-199 |
| 2101R | 22 | GB | J | | 0-0 | 23-31-32 | D06086 | | 13 | | | SM00103 | | 9 | | 001-099 |
| 2101R | 22 | GB | J | | 0-0 | 23-31-32 | D06086 | | 14 | | | SM00104 | | 9 | | 115-199 |
| 2103B | 22 | GB | U | | 6-3 | 23-31-32 | SM00104 | | | 9 | | SM00124 | | 9 | | 001-099 |
| 2103B | 22 | GB | U | | 7-0 | 23-31-32 | SM00103 | | | 9 | | SM00123 | | 9 | | 115-199 |
| 2103R | 22 | GB | U | | 0-0 | 23-31-32 | SM00103 | | | 9 | | SM00123 | | 9 | | 001-099 |
| 2103R | 22 | GB | U | | 0-0 | 23-31-32 | SM00104 | | | 9 | | SM00124 | | 9 | | 115-199 |
| 2111B | 22 | GB | K | | 8-1 | 23-31-32 | D06088 | | 14 | | | SM00124 | | 9 | | 001-099 |
| 2111B | 22 | GB | K | | 9-0 | 23-31-32 | D06088 | | 13 | | | SM00123 | | 9 | | 115-199 |
| 2111R | 22 | GB | K | | 0-0 | 23-31-32 | D06088 | | 13 | | | SM00123 | | 9 | | 001-099 |
| 2111R | 22 | GB | K | | 0-0 | 23-31-32 | D06088 | | 14 | | | SM00124 | | 9 | | 115-199 |
| 2121B | 22 | GB | L | | 11-5 | 23-31-32 | D06090 | | 14 | | | SM00124 | | 9 | | 001-099 |
| 2121B | 22 | GB | L | | 12-0 | 23-31-32 | D06090 | | 13 | | | SM00123 | | 9 | | 115-199 |
| 2121R | 22 | GB | L | | 0-0 | 23-31-32 | D06090 | | 13 | | | SM00123 | | 9 | | 001-099 |
| 2121R | 22 | GB | L | | 0-0 | 23-31-32 | D06090 | | 14 | | | SM00124 | | 9 | | 115-199 |
| 2123B | 22 | GB | V | | 5-3 | 23-31-32 | SM00124 | | | 9 | | SM00144 | | 9 | | 001-099 |
| 2123B | 22 | GB | V | | 7-0 | 23-31-32 | SM00123 | | | 9 | | SM00143 | | 9 | | 115-199 |
| 2123R | 22 | GB | V | | 0-0 | 23-31-32 | SM00123 | | | 9 | | SM00143 | | 9 | | 001-099 |
| 2123R | 22 | GB | V | | 0-0 | 23-31-32 | SM00124 | | | 9 | | SM00144 | | 9 | | 115-199 |
| 2131B | 22 | GB | M | | 7-3 | 23-31-32 | D06092 | | 14 | | | SM00144 | | 9 | | 001-099 |
| 2131B | 22 | GB | M | | 8-0 | 23-31-32 | D06092 | | 13 | | | SM00143 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 43

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | To | | | | | | | | | | |
|------------|-------------|----|-------|------------------------------------|------|----------|---------|---------|-------|------|------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice |
| W3806 | 286N3806 | | | PSU HARNESS-RIGHT, AFT (continued) | | | | | | | | | | | | |
| 2131R | 22 | GB | M | | 0-0 | 23-31-32 | D06092 | 13 | | | | SM00143 | 9 | | | 001-099 |
| 2131R | 22 | GB | M | | 0-0 | 23-31-32 | D06092 | 14 | | | | SM00144 | 9 | | | 115-199 |
| 2141B | 22 | GB | N | | 10-9 | 23-31-32 | D06094 | 14 | | | | SM00144 | 9 | | | 001-099 |
| 2141B | 22 | GB | N | | 12-0 | 23-31-32 | D06094 | 13 | | | | SM00143 | 9 | | | 115-199 |
| 2141R | 22 | GB | N | | 0-0 | 23-31-32 | D06094 | 13 | | | | SM00143 | 9 | | | 001-099 |
| 2141R | 22 | GB | N | | 0-0 | 23-31-32 | D06094 | 14 | | | | SM00144 | 9 | | | 115-199 |
| 2143B | 22 | GB | W | | 3-11 | 23-31-32 | SM00144 | | 9 | | | SM00164 | 9 | | | 001-099 |
| 2143B | 22 | GB | W | | 5-0 | 23-31-32 | SM00143 | | 9 | | | SM00163 | 9 | | | 115-199 |
| 2143R | 22 | GB | W | | 0-0 | 23-31-32 | SM00143 | | 9 | | | SM00163 | 9 | | | 001-099 |
| 2143R | 22 | GB | W | | 0-0 | 23-31-32 | SM00144 | | 9 | | | SM00164 | 9 | | | 115-199 |
| 2151B | 22 | GB | O | | 8-10 | 23-31-32 | D06096 | 14 | | | | SM00164 | 9 | | | 001-099 |
| 2151B | 22 | GB | O | | 9-0 | 23-31-32 | D06096 | 13 | | | | SM00163 | 9 | | | 115-199 |
| 2151R | 22 | GB | O | | 0-0 | 23-31-32 | D06096 | 13 | | | | SM00163 | 9 | | | 001-099 |
| 2151R | 22 | GB | O | | 0-0 | 23-31-32 | D06096 | 14 | | | | SM00164 | 9 | | | 115-199 |
| 2161B | 22 | GB | P | | 7-10 | 23-31-32 | D06098 | 14 | | | | SM00164 | 9 | | | 001-099 |
| 2161B | 22 | GB | P | | 8-0 | 23-31-32 | D06098 | 13 | | | | SM00163 | 9 | | | 115-199 |
| 2161R | 22 | GB | P | | 0-0 | 23-31-32 | D06098 | 13 | | | | SM00163 | 9 | | | 001-099 |
| 2161R | 22 | GB | P | | 0-0 | 23-31-32 | D06098 | 14 | | | | SM00164 | 9 | | | 115-199 |
| 2181B | 22 | GB | Z | | 11-7 | 23-31-32 | D07012 | 14 | | | | SM00044 | 9 | | | 001-099 |
| 2181B | 22 | GB | AB | | 13-0 | 23-31-32 | D07012 | 13 | | | | SM00043 | 9 | | | 115-199 |
| 2181R | 22 | GB | Z | | 0-0 | 23-31-32 | D07012 | 13 | | | | SM00043 | 9 | | | 001-099 |
| 2181R | 22 | GB | AB | | 0-0 | 23-31-32 | D07012 | 14 | | | | SM00044 | 9 | | | 115-199 |
| 2191B | 22 | GB | AA | | 8-6 | 23-31-32 | D07346 | 14 | | | | SM00064 | 9 | | | 001-099 |
| 2191B | 22 | GB | AA | | 9-0 | 23-31-32 | D07346 | 13 | | | | SM00063 | 9 | | | 115-199 |
| 2191R | 22 | GB | AA | | 0-0 | 23-31-32 | D07346 | 13 | | | | SM00063 | 9 | | | 001-099 |
| 2191R | 22 | GB | AA | | 0-0 | 23-31-32 | D07346 | 14 | | | | SM00064 | 9 | | | 115-199 |
| 2211B | 22 | GB | X | | 7-6 | 23-31-32 | D01245 | 1 | | | | SM00164 | 9 | | | 001-099 |
| 2211B | 22 | GB | X | | 8-0 | 23-31-32 | D01245 | 1 | | | | SM00163 | 9 | | | 115-199 |
| 2211R | 22 | GB | X | | 0-0 | 23-31-32 | D01245 | 2 | | | | SM00163 | 9 | | | 001-099 |
| 2211R | 22 | GB | X | | 0-0 | 23-31-32 | D01245 | 2 | | | | SM00164 | 9 | | | 115-199 |
| 2413B | 22 | GB | Y | | 2-7 | 23-31-32 | D40414P | 14 | | | | SM00024 | 9 | | | 001-099 |
| 2413B | 22 | GB | Y | | 3-0 | 23-31-32 | D40414P | 13 | | | | SM00023 | 9 | | | 115-199 |
| 2413R | 22 | GB | Y | | 0-0 | 23-31-32 | D40414P | 13 | | | | SM00023 | 9 | | | 001-099 |
| 2413R | 22 | GB | Y | | 0-0 | 23-31-32 | D40414P | 14 | | | | SM00024 | 9 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W3800

Page 44 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3824 | 286N3824 | | | | FLUORESCENT LIGHTING-SIDEWALL,RIGHT | | | | | | | | | | | |
| 0001 | 18 | | GA | | 9-0 | 33-21-41 | | D03804 | | | | SM00011 | | | 9 | ALL |
| 0002 | 20 | | GA | | 7-0 | 33-21-41 | | D03804 | | | | GD03570 | ST.. | E | | ALL |
| 0005 | 22 | | GA | | 9-0 | 33-21-41 | | D03804 | | | | SM00015 | | | 9 | ALL |
| 0006 | 20 | | GA | | 6-0 | 33-21-41 | | D03804 | | | | GD03532 | AC.. | E | | ALL |
| 0011 | 18 | | GA | | 9-0 | 33-21-41 | | D03806 | | | | SM00011 | | | 9 | ALL |
| 0012 | 20 | | GA | | 7-0 | 33-21-41 | | D03806 | | | | GD03570 | ST.. | E | | ALL |
| 0015 | 22 | | GA | | 9-0 | 33-21-41 | | D03806 | | | | SM00015 | | | 9 | ALL |
| 0016 | 20 | | GA | | 7-0 | 33-21-41 | | D03806 | | | | GD03532 | AC.. | E | | ALL |
| 0021 | 18 | | GA | | 10-0 | 33-21-41 | | D03808 | | | | SM00021 | | | 9 | ALL |
| 0022 | 20 | | GA | | 8-0 | 33-21-41 | | D03808 | | | | GD03571 | ST.. | E | | ALL |
| 0025 | 22 | | GA | | 10-0 | 33-21-41 | | D03808 | | | | SM00025 | | | 9 | ALL |
| 0026 | 20 | | GA | | 7-0 | 33-21-41 | | D03808 | | | | GD03533 | AC.. | E | | ALL |
| 0031 | 18 | | GA | | 10-0 | 33-21-41 | | D03810 | | | | SM00021 | | | 9 | ALL |
| 0032 | 20 | | GA | | 8-0 | 33-21-41 | | D03810 | | | | GD03571 | ST.. | E | | ALL |
| 0035 | 22 | | GA | | 10-0 | 33-21-41 | | D03810 | | | | SM00025 | | | 9 | ALL |
| 0036 | 20 | | GA | | 7-0 | 33-21-41 | | D03810 | | | | GD03533 | AC.. | E | | ALL |
| 0041 | 18 | | GA | | 15-0 | 33-21-41 | | D06302 | | | | SM00031 | | | 9 | ALL |
| 0042 | 20 | | GA | | 9-0 | 33-21-41 | | D06302 | | | | GD03572 | ST.. | E | | ALL |
| 0045 | 22 | | GA | | 15-0 | 33-21-41 | | D06302 | | | | SM00035 | | | 9 | ALL |
| 0046 | 20 | | GA | | 8-0 | 33-21-41 | | D06302 | | | | GD03534 | AC.. | E | | ALL |
| 0051 | 18 | | GA | | 15-0 | 33-21-41 | | D06304 | | | | SM00031 | | | 9 | ALL |
| 0052 | 20 | | GA | | 9-0 | 33-21-41 | | D06304 | | | | GD03572 | ST.. | E | | ALL |
| 0055 | 22 | | GA | | 15-0 | 33-21-41 | | D06304 | | | | SM00035 | | | 9 | ALL |
| 0056 | 20 | | GA | | 8-0 | 33-21-41 | | D06304 | | | | GD03534 | AC.. | E | | ALL |
| 0061 | 18 | | GA | | 17-0 | 33-21-41 | | D07472 | | | | SM00041 | | | 9 | ALL |
| 0062 | 20 | | GA | | 10-0 | 33-21-41 | | D07472 | | | | GD03574 | ST.. | E | | ALL |
| 0065 | 22 | | GA | | 17-0 | 33-21-41 | | D07472 | | | | SM00045 | | | 9 | ALL |
| 0066 | 20 | | GA | | 10-0 | 33-21-41 | | D07472 | | | | GD03535 | AC.. | E | | ALL |
| 0071 | 18 | | GA | | 17-0 | 33-21-41 | | D07474 | | | | SM00041 | | | 9 | ALL |
| 0072 | 20 | | GA | | 10-0 | 33-21-41 | | D07474 | | | | GD03574 | ST.. | E | | ALL |
| 0075 | 22 | | GA | | 17-0 | 33-21-41 | | D07474 | | | | SM00045 | | | 9 | ALL |
| 0076 | 20 | | GA | | 10-0 | 33-21-41 | | D07474 | | | | GD03535 | AC.. | E | | ALL |
| 0081 | 18 | | GA | | 14-0 | 33-21-41 | | D07476 | | | | SM00051 | | | 9 | ALL |
| 0082 | 20 | | GA | | 8-0 | 33-21-41 | | D07476 | | | | GD03575 | ST.. | E | | ALL |
| 0085 | 22 | | GA | | 14-0 | 33-21-41 | | D07476 | | | | SM00055 | | | 9 | ALL |
| 0086 | 20 | | GA | | 8-0 | 33-21-41 | | D07476 | | | | GD03536 | AC.. | E | | ALL |
| 0091 | 18 | | GA | | 14-0 | 33-21-41 | | D07478 | | | | SM00051 | | | 9 | ALL |
| 0092 | 20 | | GA | | 8-0 | 33-21-41 | | D07478 | | | | GD03575 | ST.. | E | | ALL |
| 0095 | 22 | | GA | | 14-0 | 33-21-41 | | D07478 | | | | SM00055 | | | 9 | ALL |

WIRE LIST

D280N032

91-21-11

Section W3820

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W3824 | 286N3824 | | | FLUORESCENT LIGHTING-SIDEWALL,RIGHT (continued) | | | | | | | | | | | |
| 0096 | 20 | | GA | | 8-0 | 33-21-41 | D07478 | | 6 | | GD03536 | AC.. | E | | ALL |
| 0101 | 18 | | GA | | 14-0 | 33-21-41 | D07480 | | 4 | | SM00061 | | 9 | | ALL |
| 0102 | 20 | | GA | | 6-0 | 33-21-41 | D07480 | | 5 | | GD03576 | ST.. | E | | ALL |
| 0105 | 22 | | GA | | 14-0 | 33-21-41 | D07480 | | 1 | | SM00065 | | 9 | | ALL |
| 0106 | 20 | | GA | | 6-0 | 33-21-41 | D07480 | | 6 | | GD03537 | AC.. | E | | ALL |
| 0111 | 18 | | GA | | 14-0 | 33-21-41 | D07482 | | 4 | | SM00061 | | 9 | | ALL |
| 0112 | 20 | | GA | | 6-0 | 33-21-41 | D07482 | | 5 | | GD03576 | ST.. | E | | ALL |
| 0115 | 22 | | GA | | 14-0 | 33-21-41 | D07482 | | 1 | | SM00065 | | 9 | | ALL |
| 0116 | 20 | | GA | | 6-0 | 33-21-41 | D07482 | | 6 | | GD03537 | AC.. | E | | ALL |
| 0121 | 18 | | GA | | 13-0 | 33-21-41 | D07484 | | 4 | | SM00071 | | 9 | | ALL |
| 0122 | 20 | | GA | | 7-0 | 33-21-41 | D07484 | | 5 | | GD03577 | ST.. | E | | ALL |
| 0125 | 22 | | GA | | 13-0 | 33-21-41 | D07484 | | 1 | | SM00075 | | 9 | | ALL |
| 0126 | 20 | | GA | | 7-0 | 33-21-41 | D07484 | | 6 | | GD03538 | AC.. | E | | ALL |
| 0131 | 18 | | GA | | 13-0 | 33-21-41 | D07486 | | 4 | | SM00071 | | 9 | | ALL |
| 0132 | 20 | | GA | | 7-0 | 33-21-41 | D07486 | | 5 | | GD03577 | ST.. | E | | ALL |
| 0135 | 22 | | GA | | 13-0 | 33-21-41 | D07486 | | 1 | | SM00075 | | 9 | | ALL |
| 0136 | 20 | | GA | | 7-0 | 33-21-41 | D07486 | | 6 | | GD03538 | AC.. | E | | ALL |
| 0301 | 16 | | GA | | 37-0 | 33-21-41 | D40474P | | 1 | 16 | SM00011 | | 9 | | ALL |
| 0305 | 24 | | GK | | 37-0 | 33-21-41 | D40474P | | 3 | | SM00015 | | 9 | | ALL |
| 0311 | 18 | | GA | | 10-0 | 33-21-41 | SM00011 | | | 9 | SM00021 | | 9 | | ALL |
| 0315 | 24 | | GK | | 10-0 | 33-21-41 | SM00015 | | | 9 | SM00025 | | 9 | | ALL |
| 0321 | 18 | | GA | | 12-0 | 33-21-41 | SM00021 | | | 9 | SM00031 | | 9 | | ALL |
| 0325 | 24 | | GK | | 12-0 | 33-21-41 | SM00025 | | | 9 | SM00035 | | 9 | | ALL |
| 0331 | 18 | | GA | | 20-0 | 33-21-41 | SM00031 | | | 9 | SM00041 | | 9 | | ALL |
| 0335 | 24 | | GK | | 20-0 | 33-21-41 | SM00035 | | | 9 | SM00045 | | 9 | | ALL |
| 0341 | 18 | | GA | | 17-0 | 33-21-41 | SM00041 | | | 9 | SM00051 | | 9 | | ALL |
| 0345 | 24 | | GK | | 17-0 | 33-21-41 | SM00045 | | | 9 | SM00055 | | 9 | | ALL |
| 0351 | 18 | | GA | | 15-0 | 33-21-41 | SM00051 | | | 9 | SM00061 | | 9 | | ALL |
| 0355 | 24 | | GK | | 15-0 | 33-21-41 | SM00055 | | | 9 | SM00065 | | 9 | | ALL |
| 0361 | 18 | | GA | | 16-0 | 33-21-41 | SM00061 | | | 9 | SM00071 | | 9 | | ALL |
| 0365 | 24 | | GK | | 16-0 | 33-21-41 | SM00065 | | | 9 | SM00075 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W3820

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4001 | 286N4001 | | | ATTENDANTS HANDSET DOOR 2 - RIGHT | | | | | | | | | | | |
| 4251B | 24 | G4 | AA | | 10-0 | 23-42-11 | D00889 | | | | D40009P | 3 | | | 115-199 |
| 4251G | 24 | G4 | AA | | 0-0 | 23-42-11 | D00889 | | | | D40009P | 5 | | | 115-199 |
| 4251R | 24 | G4 | AA | | 0-0 | 23-42-11 | D00889 | | | | D40009P | 1 | | | 115-199 |
| 4251Y | 24 | G4 | AA | | 0-0 | 23-42-11 | D00889 | | | | D40009P | 4 | | | 115-199 |
| 4251Z | | | AA | | 0-0 | 23-42-11 | D00889 | | | | D40009P | 2 | | | 115-199 |
| W4004 | 286N4004 | | | E/E BAY TO LEFT MIX BAY | | | | | | | | | | | |
| 0001 | 20 | GA | | | 51-0 | 21-43-11 | D41934P | | | | D02248 | 1 | | | 001-099 |
| 0001 | 20 | GA | | | 53-0 | 21-43-11 | D41934P | | | | D02248 | 1 | | | 115-199 |
| 0002 | 20 | GA | | | 51-0 | 21-43-11 | D41934P | | | | D02248 | 2 | | | 001-099 |
| 0002 | 20 | GA | | | 53-0 | 21-43-11 | D41934P | | | | D02248 | 2 | | | 115-199 |
| 0003 | 20 | GA | | | 51-0 | 21-43-11 | D41934P | | | | D02248 | 3 | | | 001-099 |
| 0003 | 20 | GA | | | 53-0 | 21-43-11 | D41934P | | | | D02248 | 3 | | | 115-199 |
| 0004 | 24 | GK | | | 51-0 | 21-43-11 | D41934P | | | | D02248 | 5 | | | 001-099 |
| 0004 | 24 | GK | | | 53-0 | 21-43-11 | D41934P | | | | D02248 | 5 | | | 115-199 |
| 0005 | 24 | GK | | | 51-0 | 21-43-11 | D41934P | | | | D02248 | 6 | | | 001-099 |
| 0005 | 24 | GK | | | 53-0 | 21-43-11 | D41934P | | | | D02248 | 6 | | | 115-199 |
| 0006 | 16 | GA | | | 3-0 | 21-43-11 | D02248 | | | | GD00126 | ST.. | E | | ALL |
| 0007 | 20 | GA | | | 8-0 | 21-43-11 | D02252 | | | | GD00127 | DC.. | E | | 001-099 |
| 0007 | 20 | GA | | | 6-0 | 21-43-11 | D02252 | | | | GD00127 | DC.. | E | | 115-199 |
| 0008 | 24 | GK | | | 40-0 | 21-43-11 | D41934P | | | | D02252 | 2 | | | 001-099 |
| 0008 | 24 | GK | | | 39-0 | 21-43-11 | D41934P | | | | D02252 | 2 | | | 115-199 |
| 0015 | 14 | GA | | | 11-0 | 21-25-11 | D41934P | | | | D02592 | 2 | | | ALL |
| 0016 | 14 | GA | | | 11-0 | 21-25-11 | D41934P | | | | D02592 | 3 | | | ALL |
| 0017 | 14 | GA | | | 11-0 | 21-25-11 | D41934P | | | | D02592 | 4 | | | ALL |
| 0018 | 14 | GA | | | 4-0 | 21-25-11 | D02592 | | | | GD00869 | ST.. | E | | ALL |
| 0019 | 24 | GK | | | 6-0 | 21-25-11 | D02592 | | | | GD01821 | AC.. | E | | ALL |
| 0020 | 24 | GK | | | 27-0 | 21-25-11 | D02592 | | | | D40056P | 22 | | | ALL |
| 0021 | 16 | GA | | | 26-0 | 21-58-13 | D01626 | | | | D40056P | 8 | | | ALL |
| 0022 | 16 | GA | | | 26-0 | 21-58-13 | D01626 | | | | D40056P | 6 | | | ALL |
| 0023 | 16 | GA | | | 26-0 | 21-58-13 | D01626 | | | | D40056P | 10 | | | ALL |
| 0024 | 16 | GA | | | 26-0 | 21-58-13 | D01626 | | | | D40056P | 1 | | | ALL |
| 0025 | 16 | GA | | | 26-0 | 21-58-13 | D01626 | | | | D40056P | 2 | | | ALL |
| 0026 | 16 | GA | | | 4-0 | 21-58-13 | D01626 | | | | GD00869 | ST.. | E | | ALL |
| 0032 | 24 | GK | | | 29-0 | 21-58-12 | D40056P | | | | D00580 | 9 | | | ALL |
| 0033 | 22 | GA | | | 20-0 | 21-58-15 | D07076 | | | | D40056P | 29 | | | ALL |
| 0034 | 22 | GA | | | 20-0 | 21-58-15 | D07076 | | | | D40056P | 30 | | | ALL |
| 0036 | 20 | GA | | | 5-0 | 21-58-12 | D00580 | | | | GD01632 | DC.. | E | | ALL |
| 0037 | 20 | GA | | | 5-0 | 21-58-12 | D00580 | | | | GD01633 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4004 | 286N4004 | | | E/E BAY TO LEFT MIX BAY (continued) | | | | | | | | | | | |
| 0038 | 20 | | GA | | 5-0 | 21-58-12 | D00580 | | 11 | | GD01632 | DC.. | E | | ALL |
| 0039 | 20 | | GA | | 3-0 | 21-58-12 | D00578 | | 3 | | GD01632 | DC.. | E | | 001-099 |
| 0039 | 20 | | GA | | 4-0 | 21-58-12 | D00578 | | 3 | | GD01632 | DC.. | E | | 115-199 |
| 0040 | 24 | | GK | | 29-0 | 21-58-12 | D00580 | | 12 | | D40056P | | | 28 | ALL |
| 0042 | 22 | | GA | | 20-0 | 21-58-15 | D07076 | | 3 | | D40056P | | | 31 | ALL |
| 0043 | 22 | | GA | | 3-0 | 21-58-15 | D07076 | | 7 | | GD03152 | ST.. | E | | ALL |
| 1001 | 24 | | G1 | AB | 30-0 | 21-58-12 | D40056P | | 27 | | D00578 | | | 7 | ALL |
| 1001Z | | | | AB | 0-0 | 21-58-12 | D40056P | | DED | | D00578 | | | DED | ALL |
| 1002 | 22 | | GT | AC | 30-0 | 21-58-12 | D40056P | | 25 | | D00578 | | | 1 | ALL |
| 1002Z | | | | AC | 0-0 | 21-58-12 | D40056P | | DED | | D00578 | | | DED | ALL |
| 1003 | 22 | | GT | AD | 30-0 | 21-58-12 | D40056P | | 26 | | D00578 | | | 4 | ALL |
| 1003Z | | | | AD | 0-0 | 21-58-12 | D40056P | | DED | | D00578 | | | DED | ALL |
| 1004 | 24 | | G1 | AE | 29-0 | 21-58-12 | D40056P | | 24 | | D00580 | | | 4 | ALL |
| 1004Z | | | | AE | 0-0 | 21-58-12 | D40056P | | DED | | D00580 | | | DED | ALL |
| W4006 | 286N4006 | | | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. | | | | | | | | | | | |
| 0001 | 24 | | GK | | 64-0 | 36-11-12 | D40060P | | 1 | | D40074J | | | 13 | 001-099 |
| 0001 | 24 | | GK | | 69-0 | 36-11-12 | D40060P | | 1 | | D40074J | | | 13 | 115-199 |
| 0003 | 22 | | GA | | 64-0 | 21-51-13 | D40060P | | 28 | | D40072J | | | 28 | 001-099 |
| 0003 | 22 | | GA | | 16-0 | 21-51-13 | D40628J | | 1 | | D40072J | | | 28 | 115-199 |
| 0004 | 22 | | GA | | 64-0 | 21-51-13 | D40060P | | 27 | | D40072J | | | 29 | 001-099 |
| 0004 | 22 | | GA | | 16-0 | 21-51-13 | D40628J | | 2 | | D40072J | | | 29 | 115-199 |
| 0005 | 22 | | GA | | 64-0 | 21-51-13 | D40060P | | 48 | | D40072J | | | 25 | 001-099 |
| 0005 | 22 | | GA | | 16-0 | 21-51-13 | D40628J | | 3 | | D40072J | | | 25 | 115-199 |
| 0006 | 22 | | GA | | 64-0 | 21-51-13 | D40060P | | 40 | | D40072J | | | 26 | 001-099 |
| 0006 | 22 | | GA | | 16-0 | 21-51-13 | D40628J | | 4 | | D40072J | | | 26 | 115-199 |
| 0029 | 24 | | GK | | 7-0 | 36-22-11 | D41544P | | 15 | | SM00002 | | | 9 | 001-099 |
| 0029 | 24 | | GK | | 10-0 | 36-22-11 | SM00002 | | | 9 | D41544P | | | 15 | 115-199 |
| 0030 | 22 | | GA | | 64-0 | 21-51-13 | D40060P | | 26 | | D40072J | | | 15 | 001-099 |
| 0030 | 22 | | GA | | 16-0 | 21-51-13 | D40628J | | 5 | | D40072J | | | 15 | 115-199 |
| 0031 | 22 | | GA | | 64-0 | 21-51-13 | D40060P | | 24 | | D40072J | | | 27 | 001-099 |
| 0031 | 22 | | GA | | 16-0 | 21-51-13 | D40628J | | 6 | | D40072J | | | 27 | 115-199 |
| 0032 | 24 | | GK | | 64-0 | 36-21-11 | D40060P | | 7 | | D40074J | | | 12 | 001-099 |
| 0032 | 24 | | GK | | 69-0 | 36-21-11 | D40060P | | 7 | | D40074J | | | 12 | 115-199 |
| 0033 | 24 | | GK | | 10-0 | 36-22-11 | D41664P | | 10 | | SM00002 | | | 9 | 001-099 |
| 0033 | 24 | | GK | | 7-0 | 36-22-11 | SM00002 | | | 9 | D41664P | | | 10 | 115-199 |
| 0034 | 24 | | GK | | 11-0 | 21-58-14 | D41544P | | 12 | | D41664P | | | 12 | 115-199 |
| 0035 | 18 | | GA | | 12-0 | 33-31-21 | SP00083 | | | 9 | D41100J | | | 15 | ALL |
| 0042 | 20 | | GA | | 64-0 | 36-11-11 | D40060P | | 11 | | D41208J | | | 1 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W4006 | 286N4006 | | | | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. (continued) | | | | | | | | | | | |
| 0042 | 20 | | GA | | 71-0 | 36-11-11 | D40060P | | 11 | | D41208J | | 1 | | 115-199 | |
| 0043 | 20 | | GA | | 64-0 | 36-11-11 | D40060P | | 12 | | D41208J | | 2 | | 001-099 | |
| 0043 | 20 | | GA | | 71-0 | 36-11-11 | D40060P | | 12 | | D41208J | | 2 | | 115-199 | |
| 0044 | 20 | | GA | | 64-0 | 36-11-11 | D40060P | | 13 | | D41208J | | 3 | | 001-099 | |
| 0044 | 20 | | GA | | 71-0 | 36-11-11 | D40060P | | 13 | | D41208J | | 3 | | 115-199 | |
| 0045 | 20 | | GA | | 64-0 | 36-11-12 | D40060P | | 14 | | D41208J | | 4 | | 001-099 | |
| 0045 | 20 | | GA | | 71-0 | 36-11-12 | D40060P | | 14 | | D41208J | | 4 | | 115-199 | |
| 0046 | 20 | | GA | | 64-0 | 36-11-12 | D40060P | | 15 | | D41208J | | 6 | | 001-099 | |
| 0046 | 20 | | GA | | 71-0 | 36-11-12 | D40060P | | 15 | | D41208J | | 6 | | 115-199 | |
| 0047 | 20 | | GA | | 5-0 | 36-11-12 | D40074J | | 14 | | D41208J | | 7 | | 001-099 | |
| 0047 | 20 | | GA | | 7-0 | 36-11-12 | D40074J | | 14 | | D41208J | | 7 | | 115-199 | |
| 0050 | 24 | | GK | | 21-0 | 21-51-14 | D40974P | | 35 | | D40060P | | 53 | | 001-099 | |
| 0050 | 24 | | GK | | 66-0 | 21-51-14 | D40974P | | 35 | | D40630J | | 1 | | 115-199 | |
| 0051 | 22 | | GA | | 17-0 | SPARE | D40628J | | 40 | | D41100J | | 13 | | 115-199 | |
| 0053 | 22 | | GA | | 57-0 | SPARE | D40846P | | 17 | | D40072J | | 14 | | 001-099 | |
| 0053 | 22 | | GA | | 16-0 | SPARE | D40628J | | 51 | | D40072J | | 14 | | 115-199 | |
| 0055 | 20 | | GA | | 71-0 | 21-51-11 | D40974P | | 1 | | D41100J | | 18 | | ALL | |
| 0056 | 20 | | GA | | 71-0 | 21-51-11 | D40974P | | 2 | | D41100J | | 19 | | ALL | |
| 0057 | 20 | | GA | | 71-0 | 21-51-11 | D40974P | | 3 | | D41100J | | 23 | | ALL | |
| 0058 | 20 | | GA | | 71-0 | 21-51-11 | D40974P | | 4 | | D41100J | | 24 | | ALL | |
| 0060 | 24 | | GK | | 71-0 | 21-51-13 | D40974P | | 6 | | D41100J | | 1 | | ALL | |
| 0061 | 24 | | GK | | 71-0 | 21-51-13 | D40974P | | 7 | | D41100J | | 2 | | ALL | |
| 0064 | 24 | | GK | | 64-0 | 36-11-12 | D40060P | | 31 | | D41208J | | 5 | | 001-099 | |
| 0064 | 24 | | GK | | 71-0 | 36-11-12 | D40060P | | 31 | | D41208J | | 5 | | 115-199 | |
| 0066 | 24 | | GK | | 23-0 | 21-51-12 | D40656P | | 8 | | D41544P | | 7 | | 001-099 | |
| 0067 | 24 | | GK | | 23-0 | 21-51-12 | D40656P | | 7 | | D41544P | | 6 | | 001-099 | |
| 0068 | 24 | | GK | | 23-0 | 21-51-12 | D40656P | | 6 | | D41544P | | 5 | | 001-099 | |
| 0069 | 24 | | GK | | 23-0 | 21-51-12 | D40656P | | 5 | | D41544P | | 4 | | 001-099 | |
| 0070 | 24 | | GK | | 23-0 | 21-51-12 | D40656P | | 4 | | D41544P | | 3 | | 001-099 | |
| 0071 | 24 | | GK | | 23-0 | 21-51-12 | D40656P | | 3 | | D41544P | | 20 | | 001-099 | |
| 0078 | 24 | | GK | | 71-0 | 21-51-13 | D40974P | | 8 | | D41100J | | 3 | | ALL | |
| 0079 | 24 | | GK | | 71-0 | 21-51-13 | D40974P | | 9 | | D41100J | | 4 | | ALL | |
| 0080 | 24 | | GK | | 71-0 | 21-51-13 | D40974P | | 10 | | D41100J | | 5 | | ALL | |
| 0081 | 24 | | GK | | 71-0 | 21-51-13 | D40974P | | 11 | | D41100J | | 6 | | ALL | |
| 0085 | 24 | | GK | | 21-0 | 21-51-13 | D40060P | | 38 | | D40974P | | 42 | | 001-099 | |
| 0085 | 24 | | GK | | 66-0 | 21-51-13 | D40630J | | 2 | | D40974P | | 42 | | 115-199 | |
| 0091 | 24 | | GK | | 21-0 | 21-51-13 | D40974P | | 19 | | D40060P | | 6 | | 001-099 | |
| 0091 | 24 | | GK | | 66-0 | 21-51-13 | D40974P | | 19 | | D40630J | | 3 | | 115-199 | |
| 0092 | 24 | | GK | | 21-0 | 21-51-13 | D40974P | | 38 | | D40060P | | 16 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|-------------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice |
| W4006 | 286N4006 | | | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. (continued) | | | | | | | | | | | | |
| 0092 | 24 | | GK | | 66-0 | 21-51-13 | D40974P | 38 | | | | D40630J | 4 | | | 115-199 |
| 0093 | 24 | | GK | | 21-0 | 21-51-13 | D40974P | 40 | | | | D40060P | 17 | | | 001-099 |
| 0093 | 24 | | GK | | 66-0 | 21-51-13 | D40974P | 40 | | | | D40630J | 5 | | | 115-199 |
| 0094 | 24 | | GK | | 21-0 | 21-51-13 | D40974P | 16 | | | | D40060P | 30 | | | 001-099 |
| 0094 | 24 | | GK | | 66-0 | 21-51-13 | D40974P | 16 | | | | D40630J | 6 | | | 115-199 |
| 0095 | 24 | | GK | | 21-0 | 21-51-13 | D40974P | 17 | | | | D40060P | 35 | | | 001-099 |
| 0095 | 24 | | GK | | 66-0 | 21-51-13 | D40974P | 17 | | | | D40630J | 7 | | | 115-199 |
| 0096 | 24 | | GK | | 21-0 | 21-51-13 | D40974P | 18 | | | | D40060P | 37 | | | 001-099 |
| 0096 | 24 | | GK | | 66-0 | 21-51-13 | D40974P | 18 | | | | D40630J | 8 | | | 115-199 |
| 0097 | 24 | | GK | | 21-0 | 21-51-13 | D40974P | 41 | | | | D41544P | 32 | | | 001-099 |
| 0097 | 24 | | GK | | 27-0 | 21-51-13 | D40974P | 41 | | | | D41544P | 32 | | | 115-199 |
| 0098 | 24 | | GK | | 21-0 | 36-11-11 | D40060P | 45 | | | | D40974P | 20 | | | 001-099 |
| 0098 | 24 | | GK | | 27-0 | 36-11-11 | D40060P | 45 | | | | D40974P | 20 | | | 115-199 |
| 0099 | 24 | | GK | | 21-0 | 21-51-13 | D40974P | 39 | | | | D40060P | 29 | | | 001-099 |
| 0099 | 24 | | GK | | 66-0 | 21-51-13 | D40974P | 39 | | | | D40630J | 9 | | | 115-199 |
| 0105 | 20 | | GA | | 64-0 | 21-61-51 | D40060P | 5 | | | | D41100J | 7 | | | 001-099 |
| 0105 | 20 | | GA | | 69-0 | 21-61-51 | D40060P | 5 | | | | D41100J | 7 | | | 115-199 |
| 0118 | 20 | | GA | | 21-0 | 36-11-11 | D40974P | 31 | | | | D40060P | 23 | | | 001-099 |
| 0118 | 20 | | GA | | 27-0 | 36-11-11 | D40974P | 31 | | | | D40060P | 23 | | | 115-199 |
| 0126 | 24 | | GK | | 21-0 | 21-51-11 | D40974P | 33 | | | | D41544P | 1 | | | 001-099 |
| 0126 | 24 | | GK | | 66-0 | 21-51-11 | D40974P | 33 | | | | D40630J | 10 | | | 115-199 |
| 0134 | 24 | | GK | | 23-0 | 21-51-12 | D40656P | 9 | | | | D41544P | 8 | | | 001-099 |
| 0135 | 24 | | GK | | 24-0 | SPARE | D40846P | 18 | | | | D40060P | 49 | | | 001-099 |
| 0135 | 24 | | GK | | 64-0 | 21-51-12 | D40630J | 11 | | | | D40060P | 49 | | | 115-199 |
| 0136 | 24 | | GK | | 63-0 | SPARE | D40630J | 48 | | | | D41544P | 13 | | | 115-199 |
| 0138 | 22 | | GA | | 24-0 | SPARE | D40846P | 20 | | | | D41544P | 14 | | | 001-099 |
| 0138 | 22 | | GA | | 62-0 | SPARE | D40632J | 43 | | | | D41544P | 14 | | | 115-199 |
| 0144 | 24 | | GK | | 5-0 | 21-52-11 | SM00005 | 9 | | 9 | | D40074J | 17 | | | 001-099 |
| 0145 | 24 | | GK | | 0-12 | 21-52-11 | SM00005 | 9 | | 9 | | GD01037 | DC.. | E | | ALL |
| 0146 | 24 | | GK | | 5-0 | 21-52-11 | SM00005 | 9 | | 9 | | D40074J | 2 | | | 001-099 |
| 0146 | 24 | | GK | | 4-0 | 21-52-11 | SM00005 | 9 | | 9 | | D40074J | 2 | | | 115-199 |
| 0147 | 24 | | GK | | 5-0 | 21-52-11 | SM00004 | 9 | | 9 | | D40074J | 4 | | | 001-099 |
| 0148 | 24 | | GK | | 0-12 | 21-52-11 | SM00004 | 9 | | 9 | | GD01037 | DC.. | E | | 001-099 |
| 0149 | 24 | | GK | | 5-0 | 21-52-11 | SM00004 | 9 | | 9 | | D40074J | 6 | | | 001-099 |
| 0150 | 24 | | GK | | 5-0 | 21-52-11 | SM00003 | 9 | | 9 | | D40074J | 9 | | | 001-099 |
| 0151 | 24 | | GK | | 0-12 | 21-52-11 | SM00003 | 9 | | 9 | | GD01037 | DC.. | E | | 001-099 |
| 0152 | 24 | | GK | | 5-0 | 21-52-11 | SM00003 | 9 | | 9 | | D40074J | 11 | | | 001-099 |
| 0160 | 24 | | GK | | 21-0 | 21-51-15 | D40060P | 20 | | | | D40974P | 52 | | | 001-099 |
| 0160 | 24 | | GK | | 66-0 | 21-51-15 | D40630J | 12 | | | | D40974P | 52 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4006 | 286N4006 | | | | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. (continued) | | | | | | | | | | | | |
| 0161 | 24 | | GK | | 24-0 | 21-51-15 | D40060P | 21 | | | D40656P | 42 | | | 001-099 | | |
| 0162 | 24 | | GK | | 21-0 | 21-51-15 | D40974P | 51 | | | D40060P | 19 | | | 001-099 | | |
| 0162 | 24 | | GK | | 66-0 | 21-51-15 | D40974P | 51 | | | D40630J | 13 | | | 115-199 | | |
| 0163 | 24 | | GK | | 27-0 | 21-51-15 | D40656P | 43 | | | D41664P | 2 | | | 001-099 | | |
| 0163 | 24 | | GK | | 60-0 | 21-51-15 | D40632J | 1 | | | D41664P | 2 | | | 115-199 | | |
| 0164 | 24 | | GK | | 24-0 | 21-51-15 | D40060P | 22 | | | D40656P | 53 | | | 001-099 | | |
| 0165 | 24 | | GK | | 71-0 | 21-51-15 | D40974P | 32 | | | D41100J | 8 | | | ALL | | |
| 0166 | 24 | | GK | | 71-0 | 21-51-15 | D40974P | 23 | | | D41100J | 9 | | | ALL | | |
| 0185 | 22 | | GA | | 60-0 | 32-42-11 | D41664P | 40 | | | D40632J | 2 | | | 115-199 | | |
| 0209 | 24 | | GK | | 59-0 | 36-22-11 | SM00002 | | 9 | | D40072J | 35 | | | 001-099 | | |
| 0209 | 24 | | GK | | 61-0 | 36-22-11 | SM00002 | | 9 | | D40072J | 35 | | | 115-199 | | |
| 0211 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 20 | | | D40632J | 3 | | | 115-199 | | |
| 0212 | 22 | | GA | | 15-0 | 32-42-11 | D41544P | 38 | | | D40190P | 6 | | | 001-099 | | |
| 0212 | 22 | | GA | | 63-0 | 32-42-11 | D41544P | 38 | | | D40630J | 14 | | | 115-199 | | |
| 0213 | 22 | | GA | | 15-0 | 32-42-11 | D41544P | 39 | | | D40190P | 7 | | | 001-099 | | |
| 0213 | 22 | | GA | | 63-0 | 32-42-11 | D41544P | 39 | | | D40630J | 15 | | | 115-199 | | |
| 0214 | 22 | | GA | | 15-0 | 32-42-11 | D41544P | 40 | | | D40190P | 9 | | | 001-099 | | |
| 0214 | 22 | | GA | | 63-0 | 32-42-11 | D41544P | 40 | | | D40630J | 16 | | | 115-199 | | |
| 0215 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 1 | | | D40632J | 4 | | | 115-199 | | |
| 0216 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 32 | | | D40632J | 5 | | | 115-199 | | |
| 0217 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 3 | | | D40632J | 6 | | | 115-199 | | |
| 0218 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 4 | | | D40632J | 7 | | | 115-199 | | |
| 0219 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 5 | | | D40632J | 8 | | | 115-199 | | |
| 0220 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 6 | | | D40632J | 9 | | | 115-199 | | |
| 0221 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 7 | | | D40632J | 10 | | | 115-199 | | |
| 0222 | 24 | | GK | | 60-0 | 32-46-11 | D41664P | 8 | | | D40632J | 11 | | | 115-199 | | |
| 0223 | 24 | | GK | | 60-0 | 32-41-11 | D41664P | 21 | | | D40632J | 12 | | | 115-199 | | |
| 0232 | 24 | | GK | | 15-0 | 32-42-11 | D41544P | 41 | | | D40190P | 10 | | | 001-099 | | |
| 0232 | 24 | | GK | | 63-0 | 32-42-11 | D41544P | 41 | | | D40630J | 17 | | | 115-199 | | |
| 0235 | 24 | | GK | | 63-0 | SPARE | D41544P | 53 | | | D40630J | 18 | | | 115-199 | | |
| 0237 | 22 | | GA | | 15-0 | 32-42-12 | D41544P | 42 | | | D40190P | 1 | | | 001-099 | | |
| 0237 | 22 | | GA | | 63-0 | 32-42-12 | D41544P | 42 | | | D40630J | 19 | | | 115-199 | | |
| 0238 | 22 | | GA | | 15-0 | 32-42-12 | D41544P | 43 | | | D40190P | 2 | | | 001-099 | | |
| 0238 | 22 | | GA | | 63-0 | 32-42-12 | D41544P | 43 | | | D40630J | 20 | | | 115-199 | | |
| 0239 | 24 | | GK | | 29-0 | 21-61-51 | D40846P | 16 | | | D42084P | 41 | | | 001-099 | | |
| 0239 | 24 | | GK | | 61-0 | 21-61-51 | D40632J | 20 | | | D42084P | 55 | | | 115-199 | | |
| 0242 | 24 | | GK | | 63-0 | 21-58-11 | D40630J | 21 | | | D41544P | 19 | | | 115-199 | | |
| 0245 | 24 | | GK | | 63-0 | 21-58-11 | D40630J | 22 | | | D41544P | 24 | | | 115-199 | | |
| 0246 | 20 | | GA | | 63-0 | 21-58-11 | D40630J | 23 | | | D41544P | 46 | | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4006 | 286N4006 | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. (continued) | | | | | | | | | | | | | |
| 0250 | 22 | GA | | | 63-0 | 21-58-24 | D40630J | 25 | | | D41544P | 29 | | | 115-199 |
| 0251 | 22 | GA | | | 63-0 | 21-58-24 | D40630J | 26 | | | D41544P | 28 | | | 115-199 |
| 0252 | 22 | GA | | | 63-0 | 21-58-24 | D40630J | 27 | | | D41544P | 27 | | | 115-199 |
| 0253 | 22 | GA | | | 63-0 | 21-58-24 | D40630J | 28 | | | D41544P | 30 | | | 115-199 |
| 0254 | 22 | GA | | | 63-0 | 21-58-24 | D40630J | 29 | | | D41544P | 31 | | | 115-199 |
| 0257 | 20 | GA | | | 24-0 | 21-51-12 | D40060P | 25 | | | D40656P | 1 | | | 001-099 |
| 0257 | 20 | GA | | | 64-0 | 21-51-12 | D40060P | 25 | | | D40630J | 30 | | | 115-199 |
| 0259 | 24 | GK | | | 24-0 | 21-61-51 | D41544P | 55 | | | D40846P | 3 | | | 001-099 |
| 0259 | 24 | GK | | | 63-0 | 21-61-51 | D41544P | 55 | | | D40630J | 31 | | | 115-199 |
| 0261 | 24 | GK | | | 63-0 | SPARE | D41544P | 51 | | | D40630J | 32 | | | 115-199 |
| 0266 | 24 | GK | | | 24-0 | 21-51-14 | D40656P | 12 | | | D40060P | 51 | | | 001-099 |
| 0267 | 22 | GA | | | 13-0 | 32-42-11 | D41544P | 48 | | | D41664P | 11 | | | 001-099 |
| 0267 | 22 | GA | | | 11-0 | 32-42-11 | D41544P | 48 | | | D41664P | 41 | | | 115-199 |
| 0268 | 22 | GA | | | 13-0 | 32-42-11 | D41544P | 49 | | | D41664P | 12 | | | 001-099 |
| 0268 | 22 | GA | | | 11-0 | 32-42-11 | D41544P | 49 | | | D41664P | 39 | | | 115-199 |
| 0269 | 22 | GA | | | 15-0 | 32-42-11 | D41544P | 26 | | | D40190P | 8 | | | 001-099 |
| 0269 | 22 | GA | | | 63-0 | 32-42-11 | D41544P | 26 | | | D40630J | 41 | | | 115-199 |
| 0270 | 22 | GA | | | 13-0 | 32-42-11 | D41544P | 47 | | | D41664P | 9 | | | 001-099 |
| 0270 | 22 | GA | | | 11-0 | 32-42-11 | D41544P | 47 | | | D41664P | 38 | | | 115-199 |
| 0272 | 22 | GA | | | 13-0 | SPARE | D41544P | 50 | | | D41664P | 1 | | | 001-099 |
| 0272 | 22 | GA | | | 11-0 | SPARE | D41544P | 50 | | | D41664P | 30 | | | 115-199 |
| 0273 | 22 | GA | | | 64-0 | SPARE | D40630J | 43 | | | D40060P | 41 | | | 115-199 |
| 0301 | 22 | GA | | | 63-0 | SPARE | D40632J | 44 | | | D40060P | 44 | | | 115-199 |
| 0302 | 22 | GA | | | 62-0 | SPARE | D40632J | 32 | | | D41544P | 2 | | | 115-199 |
| 0303 | 22 | GA | | | 63-0 | SPARE | D40632J | 33 | | | D40060P | 34 | | | 115-199 |
| 0309 | 22 | GA | | | 66-0 | SPARE | D40630J | 50 | | | D40974P | 50 | | | 115-199 |
| 0311 | 22 | GA | | | 62-0 | SPARE | D40630J | 52 | | | D42084P | 52 | | | 115-199 |
| 1001 | 22 | GT | AI | | 63-0 | SPARE | D41544P | 52 | | | D40630J | 40 | | | 115-199 |
| 1001Z | | | AI | | 0-0 | SPARE | D41544P | DED | | | D40630J | DED | | | 115-199 |
| 2001B | 24 | GL | AB | | 64-0 | 36-21-11 | D40060P | 47 | | | D40074J | 24 | | | 001-099 |
| 2001B | 24 | GL | AB | | 69-0 | 36-21-11 | D40060P | 47 | | | D40074J | 24 | | | 115-199 |
| 2001R | 24 | GL | AB | | 0-0 | 36-21-11 | D40060P | 46 | | | D40074J | 23 | | | ALL |
| 2002B | 24 | GL | AC | | 16-0 | SPARE | D40628J | 46 | | | D40072J | 23 | | | 115-199 |
| 2002R | 24 | GL | AC | | 0-0 | SPARE | D40628J | 47 | | | D40072J | 24 | | | 115-199 |
| 2004B | 24 | GL | AE | | 69-0 | 21-52-11 | D42084P | 32 | | | D40074J | 16 | | | 001-099 |
| 2004R | 24 | GL | AE | | 0-0 | 21-52-11 | D42084P | 33 | | | SM00005 | | 9 | | 001-099 |
| 2007B | 24 | GL | AM | | 69-0 | 21-52-11 | D42084P | 1 | | | D40074J | 1 | | | 001-099 |
| 2007B | 24 | GL | AM | | 68-0 | 21-52-11 | D42084P | 1 | | | D40074J | 1 | | | 115-199 |
| 2007R | 24 | GL | AM | | 0-0 | 21-52-11 | D42084P | 2 | | | SM00005 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4006 | 286N4006 | | | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. (continued) | | | | | | | | | | | |
| 2008B | 24 | GL | AN | | 69-0 | 21-52-11 | D42084P | | 3 | | D40074J | | 3 | | 001-099 |
| 2008R | 24 | GL | AN | | 0-0 | 21-52-11 | D42084P | | 4 | | SM00004 | | 9 | | 001-099 |
| 2009B | 24 | GL | AO | | 69-0 | 21-52-11 | D42084P | | 5 | | D40074J | | 5 | | 001-099 |
| 2009R | 24 | GL | AO | | 0-0 | 21-52-11 | D42084P | | 6 | | SM00004 | | 9 | | 001-099 |
| 2010B | 24 | GL | AP | | 69-0 | 21-52-11 | D42084P | | 7 | | D40074J | | 7 | | 001-099 |
| 2010R | 24 | GL | AP | | 0-0 | 21-52-11 | D42084P | | 8 | | SM00003 | | 9 | | 001-099 |
| 2011B | 24 | GL | AQ | | 69-0 | 21-52-11 | D42084P | | 9 | | D40074J | | 10 | | 001-099 |
| 2011R | 24 | GL | AQ | | 0-0 | 21-52-11 | D42084P | | 10 | | SM00003 | | 9 | | 001-099 |
| 2012B | 24 | GL | BA | | 57-0 | 21-51-14 | D40656P | | 49 | | D40072J | | 49 | | 001-099 |
| 2012B | 24 | GL | BA | | 16-0 | 21-51-14 | D40628J | | 7 | | D40072J | | 49 | | 115-199 |
| 2012R | 24 | GL | BA | | 0-0 | 21-51-14 | D40656P | | 48 | | D40072J | | 47 | | 001-099 |
| 2012R | 24 | GL | BA | | 0-0 | 21-51-14 | D40628J | | 8 | | D40072J | | 47 | | 115-199 |
| 2013B | 24 | GL | DG | | 24-0 | 21-51-14 | D40656P | | 51 | | D40060P | | 18 | | 001-099 |
| 2013R | 24 | GL | DG | | 0-0 | 21-51-14 | D40656P | | 50 | | D40060P | | 4 | | 001-099 |
| 2014B | 24 | GL | DH | | 24-0 | 21-51-14 | D40656P | | 40 | | D40060P | | 2 | | 001-099 |
| 2014R | 24 | GL | DH | | 0-0 | 21-51-14 | D40656P | | 41 | | D40060P | | 3 | | 001-099 |
| 2015B | 24 | GL | BE | | 64-0 | 21-51-14 | D40060P | | 54 | | D40072J | | 51 | | 001-099 |
| 2015B | 24 | GL | BE | | 16-0 | 21-51-14 | D40628J | | 9 | | D40072J | | 51 | | 115-199 |
| 2015R | 24 | GL | BE | | 0-0 | 21-51-14 | D40060P | | 55 | | D40072J | | 50 | | 001-099 |
| 2015R | 24 | GL | BE | | 0-0 | 21-51-14 | D40628J | | 10 | | D40072J | | 50 | | 115-199 |
| 2029B | 24 | GL | AA | | 57-0 | 21-51-14 | D40656P | | 47 | | D40072J | | 39 | | 001-099 |
| 2029B | 24 | GL | AA | | 16-0 | 21-51-14 | D40628J | | 11 | | D40072J | | 39 | | 115-199 |
| 2029R | 24 | GL | AA | | 0-0 | 21-51-14 | D40656P | | 46 | | D40072J | | 38 | | 001-099 |
| 2029R | 24 | GL | AA | | 0-0 | 21-51-14 | D40628J | | 12 | | D40072J | | 38 | | 115-199 |
| 2033B | 24 | GL | AF | | 69-0 | 21-52-31 | D42084P | | 18 | | D40074J | | 18 | | 001-099 |
| 2033B | 24 | GL | AF | | 68-0 | 21-52-31 | D42084P | | 18 | | D40074J | | 18 | | 115-199 |
| 2033R | 24 | GL | AF | | 0-0 | 21-52-31 | D42084P | | 17 | | D40074J | | 19 | | ALL |
| 2035B | 24 | GL | AH | | 69-0 | 21-52-31 | D42084P | | 23 | | D40074J | | 20 | | 001-099 |
| 2035B | 24 | GL | AH | | 68-0 | 21-52-31 | D42084P | | 23 | | D40074J | | 20 | | 115-199 |
| 2035R | 24 | GL | AH | | 0-0 | 21-52-31 | D42084P | | 22 | | D40074J | | 21 | | ALL |
| 2036B | 24 | GL | AJ | | 15-0 | 36-21-11 | D42084P | | 25 | | D40060P | | 42 | | 001-099 |
| 2036B | 24 | GL | AJ | | 68-0 | 36-21-11 | D42084P | | 25 | | D40074J | | 34 | | 115-199 |
| 2036R | 24 | GL | AJ | | 0-0 | 36-21-11 | D42084P | | 24 | | D40060P | | 43 | | 001-099 |
| 2036R | 24 | GL | AJ | | 0-0 | 36-21-11 | D42084P | | 24 | | D40074J | | 35 | | 115-199 |
| 2038B | 24 | GL | DA | | 68-0 | 36-22-21 | D42084P | | 26 | | D41208J | | 12 | | 001-099 |
| 2038B | 24 | GL | AL | | 69-0 | 36-22-21 | D42084P | | 26 | | D41208J | | 12 | | 115-199 |
| 2038R | 24 | GL | DA | | 0-0 | 36-22-21 | D42084P | | 27 | | D41208J | | 13 | | 001-099 |
| 2038R | 24 | GL | AL | | 0-0 | 36-22-21 | D42084P | | 27 | | D41208J | | 13 | | 115-199 |
| 2040B | 24 | GL | DF | | 23-0 | 21-51-12 | D40656P | | 11 | | D41544P | | 10 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4006 | 286N4006 | | | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. (continued) | | | | | | | | | | | |
| 2040R | 24 | GL | DF | | 0-0 | 21-51-12 | D40656P | 10 | | | D41544P | 9 | | | 001-099 |
| 2041B | 24 | GL | AT | | 64-0 | 21-51-12 | D41544P | 11 | | | D40072J | 46 | | | 001-099 |
| 2041B | 24 | GL | AT | | 16-0 | 21-51-12 | D40628J | 13 | | | D40072J | 46 | | | 115-199 |
| 2041R | 24 | GL | AT | | 0-0 | 21-51-12 | D41544P | 21 | | | D40072J | 45 | | | 001-099 |
| 2041R | 24 | GL | AT | | 0-0 | 21-51-12 | D40628J | 14 | | | D40072J | 45 | | | 115-199 |
| 2042B | 24 | GL | BG | | 57-0 | 21-51-15 | D40656P | 44 | | | D40072J | 52 | | | 001-099 |
| 2042B | 24 | GL | BG | | 16-0 | 21-51-15 | D40628J | 15 | | | D40072J | 52 | | | 115-199 |
| 2042R | 24 | GL | BG | | 0-0 | 21-51-15 | D40656P | 45 | | | D40072J | 53 | | | 001-099 |
| 2042R | 24 | GL | BG | | 0-0 | 21-51-15 | D40628J | 16 | | | D40072J | 53 | | | 115-199 |
| 2043B | 24 | GL | DL | | 9-0 | 21-61-51 | D40774P | 4 | | | D40846P | 5 | | | 001-099 |
| 2043R | 24 | GL | DL | | 0-0 | 21-61-51 | D40774P | 3 | | | D40846P | 4 | | | 001-099 |
| 2044B | 24 | GL | DM | | 9-0 | 21-61-51 | D40774P | 6 | | | D40846P | 7 | | | 001-099 |
| 2044R | 24 | GL | DM | | 0-0 | 21-61-51 | D40774P | 5 | | | D40846P | 6 | | | 001-099 |
| 2045B | 24 | GL | DN | | 9-0 | 21-61-51 | D40774P | 8 | | | D40846P | 9 | | | 001-099 |
| 2045R | 24 | GL | DN | | 0-0 | 21-61-51 | D40774P | 7 | | | D40846P | 8 | | | 001-099 |
| 2046B | 24 | GL | DP | | 9-0 | 21-61-51 | D40774P | 10 | | | D40846P | 11 | | | 001-099 |
| 2046R | 24 | GL | DP | | 0-0 | 21-61-51 | D40774P | 9 | | | D40846P | 10 | | | 001-099 |
| 2047B | 24 | GL | DR | | 9-0 | 21-61-51 | D40774P | 12 | | | D40846P | 13 | | | 001-099 |
| 2047R | 24 | GL | DR | | 0-0 | 21-61-51 | D40774P | 11 | | | D40846P | 12 | | | 001-099 |
| 2049B | 24 | GL | CB | | 24-0 | 21-51-12 | D40656P | 15 | | | D40060P | 32 | | | 001-099 |
| 2049B | 24 | GL | CB | | 64-0 | 21-51-12 | D40630J | 33 | | | D40060P | 32 | | | 115-199 |
| 2049R | 24 | GL | CB | | 0-0 | 21-51-12 | D40656P | 16 | | | D40060P | 33 | | | 001-099 |
| 2049R | 24 | GL | CB | | 0-0 | 21-51-12 | D40630J | 34 | | | D40060P | 33 | | | 115-199 |
| 2050B | 24 | GL | BR | | 24-0 | 21-61-51 | D41544P | 34 | | | D40846P | 2 | | | 001-099 |
| 2050B | 24 | GL | BR | | 63-0 | 21-61-51 | D41544P | 34 | | | D40630J | 35 | | | 115-199 |
| 2050R | 24 | GL | BR | | 0-0 | 21-61-51 | D41544P | 33 | | | D40846P | 1 | | | 001-099 |
| 2050R | 24 | GL | BR | | 0-0 | 21-61-51 | D41544P | 33 | | | D40630J | 36 | | | 115-199 |
| 2051B | 24 | GL | CA | | 57-0 | 21-51-12 | D40072J | 32 | | | D40656P | 21 | | | 001-099 |
| 2051B | 24 | GL | CA | | 16-0 | 21-51-12 | D40072J | 32 | | | D40628J | 17 | | | 115-199 |
| 2051R | 24 | GL | CA | | 0-0 | 21-51-12 | D40072J | 31 | | | D40656P | 20 | | | 001-099 |
| 2051R | 24 | GL | CA | | 0-0 | 21-51-12 | D40072J | 31 | | | D40628J | 18 | | | 115-199 |
| 2052B | 24 | GL | DJ | | 40-2 | 21-61-21 | D02568 | 2 | | | D40846P | 22 | | | 001-099 |
| 2052R | 24 | GL | DJ | | 0-0 | 21-61-21 | D02568 | 1 | | | D40846P | 21 | | | 001-099 |
| 2053B | 24 | GL | DK | | 38-5 | 21-61-21 | D02568 | 4 | | | D40774P | 2 | | | 001-099 |
| 2053R | 24 | GL | DK | | 0-0 | 21-61-21 | D02568 | 3 | | | D40774P | 1 | | | 001-099 |
| 2054B | 24 | GL | DC | | 55-0 | 21-51-12 | D40656P | 14 | | | D02954 | 1 | | | 001-099 |
| 2054B | 24 | GL | DC | | 14-0 | 21-51-12 | D40632J | 21 | | | D02954 | 1 | | | 115-199 |
| 2054R | 24 | GL | DC | | 0-0 | 21-51-12 | D40656P | 13 | | | D02954 | 2 | | | 001-099 |
| 2054R | 24 | GL | DC | | 0-0 | 21-51-12 | D40632J | 22 | | | D02954 | 2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4006 | 286N4006 | | | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. (continued) | | | | | | | | | | | |
| 3001B | 24 | GM | AU | | 57-0 | 21-51-12 | D40656P | 23 | | | D40072J | 4 | | | 001-099 |
| 3001B | 24 | GM | AU | | 16-0 | 21-51-12 | D40628J | 19 | | | D40072J | 4 | | | 115-199 |
| 3001R | 24 | GM | AU | | 0-0 | 21-51-12 | D40656P | 22 | | | D40072J | 5 | | | 001-099 |
| 3001R | 24 | GM | AU | | 0-0 | 21-51-12 | D40628J | 20 | | | D40072J | 5 | | | 115-199 |
| 3001Y | 24 | GM | AU | | 0-0 | 21-51-12 | D40656P | 24 | | | D40072J | 6 | | | 001-099 |
| 3001Y | 24 | GM | AU | | 0-0 | 21-51-12 | D40628J | 21 | | | D40072J | 6 | | | 115-199 |
| 3002B | 24 | GM | AV | | 57-0 | 21-51-12 | D40656P | 26 | | | D40072J | 2 | | | 001-099 |
| 3002B | 24 | GM | AV | | 16-0 | 21-51-12 | D40628J | 22 | | | D40072J | 2 | | | 115-199 |
| 3002R | 24 | GM | AV | | 0-0 | 21-51-12 | D40656P | 25 | | | D40072J | 1 | | | 001-099 |
| 3002R | 24 | GM | AV | | 0-0 | 21-51-12 | D40628J | 23 | | | D40072J | 1 | | | 115-199 |
| 3002Y | 24 | GM | AV | | 0-0 | 21-51-12 | D40656P | 27 | | | D40072J | 3 | | | 001-099 |
| 3002Y | 24 | GM | AV | | 0-0 | 21-51-12 | D40628J | 24 | | | D40072J | 3 | | | 115-199 |
| 3003B | 24 | GM | AW | | 57-0 | 21-51-12 | D40656P | 29 | | | D40072J | 12 | | | 001-099 |
| 3003B | 24 | GM | AW | | 16-0 | 21-51-12 | D40628J | 25 | | | D40072J | 12 | | | 115-199 |
| 3003R | 24 | GM | AW | | 0-0 | 21-51-12 | D40656P | 28 | | | D40072J | 11 | | | 001-099 |
| 3003R | 24 | GM | AW | | 0-0 | 21-51-12 | D40628J | 26 | | | D40072J | 11 | | | 115-199 |
| 3003Y | 24 | GM | AW | | 0-0 | 21-51-12 | D40656P | 30 | | | D40072J | 13 | | | 001-099 |
| 3003Y | 24 | GM | AW | | 0-0 | 21-51-12 | D40628J | 27 | | | D40072J | 13 | | | 115-199 |
| 3004B | 24 | GM | AX | | 57-0 | 21-51-12 | D40656P | 32 | | | D40072J | 9 | | | 001-099 |
| 3004B | 24 | GM | AX | | 16-0 | 21-51-12 | D40628J | 28 | | | D40072J | 9 | | | 115-199 |
| 3004R | 24 | GM | AX | | 0-0 | 21-51-12 | D40656P | 31 | | | D40072J | 8 | | | 001-099 |
| 3004R | 24 | GM | AX | | 0-0 | 21-51-12 | D40628J | 29 | | | D40072J | 8 | | | 115-199 |
| 3004Y | 24 | GM | AX | | 0-0 | 21-51-12 | D40656P | 33 | | | D40072J | 10 | | | 001-099 |
| 3004Y | 24 | GM | AX | | 0-0 | 21-51-12 | D40628J | 30 | | | D40072J | 10 | | | 115-199 |
| 3005B | 24 | GM | AY | | 57-0 | 21-51-12 | D40656P | 35 | | | D40072J | 18 | | | 001-099 |
| 3005B | 24 | GM | AY | | 16-0 | 21-51-12 | D40628J | 31 | | | D40072J | 18 | | | 115-199 |
| 3005R | 24 | GM | AY | | 0-0 | 21-51-12 | D40656P | 34 | | | D40072J | 19 | | | 001-099 |
| 3005R | 24 | GM | AY | | 0-0 | 21-51-12 | D40628J | 32 | | | D40072J | 19 | | | 115-199 |
| 3005Y | 24 | GM | AY | | 0-0 | 21-51-12 | D40656P | 36 | | | D40072J | 20 | | | 001-099 |
| 3005Y | 24 | GM | AY | | 0-0 | 21-51-12 | D40628J | 33 | | | D40072J | 20 | | | 115-199 |
| 3006B | 24 | GM | AZ | | 57-0 | 21-51-12 | D40656P | 38 | | | D40072J | 16 | | | 001-099 |
| 3006B | 24 | GM | AZ | | 16-0 | 21-51-12 | D40628J | 34 | | | D40072J | 16 | | | 115-199 |
| 3006R | 24 | GM | AZ | | 0-0 | 21-51-12 | D40656P | 37 | | | D40072J | 7 | | | 001-099 |
| 3006R | 24 | GM | AZ | | 0-0 | 21-51-12 | D40628J | 35 | | | D40072J | 7 | | | 115-199 |
| 3006Y | 24 | GM | AZ | | 0-0 | 21-51-12 | D40656P | 39 | | | D40072J | 17 | | | 001-099 |
| 3006Y | 24 | GM | AZ | | 0-0 | 21-51-12 | D40628J | 36 | | | D40072J | 17 | | | 115-199 |
| 3009B | 24 | GM | BB | | 57-0 | 21-51-12 | D40072J | 37 | | | D40656P | 19 | | | 001-099 |
| 3009B | 24 | GM | BB | | 16-0 | 21-51-12 | D40072J | 37 | | | D40628J | 37 | | | 115-199 |
| 3009R | 24 | GM | BB | | 0-0 | 21-51-12 | D40072J | 34 | | | D40656P | 17 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 9

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4006 | 286N4006 | | | E/E BAY TO L. W/B DISC-AIR CONDITIONING SYST. (continued) | | | | | | | | | | | |
| 3009R | 24 | GM | BB | | 0-0 | 21-51-12 | D40072J | 34 | | | D40628J | 38 | | | 115-199 |
| 3009Y | 24 | GM | BB | | 0-0 | 21-51-12 | D40072J | 36 | | | D40656P | 18 | | | 001-099 |
| 3009Y | 24 | GM | BB | | 0-0 | 21-51-12 | D40072J | 36 | | | D40628J | 39 | | | 115-199 |
| 3020B | 24 | GM | CL | | 69-0 | 21-52-21 | D42084P | 12 | | | D40074J | 39 | | | 001-099 |
| 3020B | 24 | GM | CL | | 68-0 | 21-52-21 | D42084P | 12 | | | D40074J | 39 | | | 115-199 |
| 3020R | 24 | GM | CL | | 0-0 | 21-52-21 | D42084P | 11 | | | D40074J | 38 | | | ALL |
| 3020Y | 24 | GM | CL | | 0-0 | 21-52-21 | D42084P | 13 | | | D40074J | 40 | | | ALL |
| 3021B | 24 | GM | CM | | 69-0 | 21-52-21 | D42084P | 15 | | | D40074J | 28 | | | 001-099 |
| 3021B | 24 | GM | CM | | 68-0 | 21-52-21 | D42084P | 15 | | | D40074J | 28 | | | 115-199 |
| 3021R | 24 | GM | CM | | 0-0 | 21-52-21 | D42084P | 16 | | | D40074J | 27 | | | ALL |
| 3021Y | 24 | GM | CM | | 0-0 | 21-52-21 | D42084P | 14 | | | D40074J | 29 | | | ALL |
| 4000B | 24 | GN | CN | | 69-0 | 21-52-31 | D42084P | 20 | | | D40074J | 32 | | | 001-099 |
| 4000B | 24 | GN | CN | | 68-0 | 21-52-31 | D42084P | 20 | | | D40074J | 32 | | | 115-199 |
| 4000G | 24 | GN | CN | | 0-0 | 21-52-31 | D42084P | 40 | | | D40074J | 30 | | | ALL |
| 4000R | 24 | GN | CN | | 0-0 | 21-52-31 | D42084P | 19 | | | D40074J | 31 | | | ALL |
| 4000Y | 24 | GN | CN | | 0-0 | 21-52-31 | D42084P | 21 | | | D40074J | 33 | | | ALL |
| 5001B | 22 | GU | CC | | 15-0 | 32-42-11 | D41544P | 36 | | | D40190P | 4 | | | 001-099 |
| 5001B | 22 | GU | CC | | 63-0 | 32-42-11 | D41544P | 36 | | | D40630J | 37 | | | 115-199 |
| 5001R | 22 | GU | CC | | 0-0 | 32-42-11 | D41544P | 35 | | | D40190P | 3 | | | 001-099 |
| 5001R | 22 | GU | CC | | 0-0 | 32-42-11 | D41544P | 35 | | | D40630J | 38 | | | 115-199 |
| 5001Z | | | CC | | 0-0 | 32-42-11 | D41544P | 37 | | | D40190P | 5 | | | 001-099 |
| 5001Z | | | CC | | 0-0 | 32-42-11 | D41544P | 37 | | | D40630J | 39 | | | 115-199 |
| YAAA | | | | | 0-0 | 21-52-11 | GD00464 | ST.. | E | | D40074J | S/R | | | ALL |
| YAAB | | | | | 0-0 | 21-51-14 | GD00464 | ST.. | E | | D40072J | S/R | | | ALL |
| YAAC | | | | | 0-0 | 21-51-11 | GD02561 | ST.. | E | | D41100J | S/R | | | 001-099 |
| YAAC | | | | | 0-0 | 21-51-11 | GD00464 | ST.. | E | | D41100J | S/R | | | 115-199 |
| YAAD | | | | | 0-0 | 36-11-11 | GD00464 | ST.. | E | | D41208J | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4000

Page 10 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4018 | 286N4018 | | | E5 RACK TO AA1705 DISC. BRACKET | | | | | | | | | | | |
| 0003 | 22 | | GA | | 116-0 | 33-31-31 | D42120P | | 11 | | D40258P | | 3 | | 001-099 |
| 0003 | 22 | | GA | | 117-0 | 33-31-31 | D41644P | | 3 | | D40258J | | 3 | | 115-199 |
| 0012 | 22 | | GA | | 11-0 | 24-22-41 | D41644P | | 1 | | SP00208 | | 9 | | 115-199 |
| 0013 | 20 | | GA | | 116-0 | SPARE | D42120P | | 12 | | D40258P | | 2 | | 001-099 |
| 0013 | 20 | | GA | | 117-0 | SPARE | D41644P | | 2 | | D40258J | | 2 | | 115-199 |
| 0014 | 20 | | GA | | 116-0 | SPARE | D42120P | | 13 | | D40258P | | 14 | | 001-099 |
| 0014 | 20 | | GA | | 117-0 | SPARE | D41644P | | 4 | | D40258J | | 14 | | 115-199 |
| 2501B | 20 | | GU | AB | 116-0 | 24-21-41 | D42120P | | 9 | | D40258P | | 9 | | 001-099 |
| 2501B | 20 | | GU | AB | 117-0 | 24-21-41 | D41644P | | 9 | | D40258J | | 9 | | 115-199 |
| 2501R | 20 | | GU | AB | 0-0 | 24-21-41 | D42120P | | 8 | | D40258P | | 8 | | 001-099 |
| 2501R | 20 | | GU | AB | 0-0 | 24-21-41 | D41644P | | 8 | | D40258J | | 8 | | 115-199 |
| 2501Z | | | | AB | 0-0 | 24-21-41 | D42120P | | 10 | | D40258P | | 4 | | 001-099 |
| 2501Z | | | | AB | 0-0 | 24-21-41 | D41644P | | 14 | | D40258J | | 4 | | 115-199 |
| 3001B | 18 | | GC | AA | 116-0 | 24-21-41 | D42120P | | 2 | | D40258P | | 6 | | 001-099 |
| 3001B | 18 | | GC | AA | 117-0 | 24-21-41 | D41644P | | 6 | | D40258J | | 6 | | 115-199 |
| 3001R | 18 | | GC | AA | 0-0 | 24-21-41 | D42120P | | 1 | | D40258P | | 5 | | 001-099 |
| 3001R | 18 | | GC | AA | 0-0 | 24-21-41 | D41644P | | 5 | | D40258J | | 5 | | 115-199 |
| 3001Y | 18 | | GC | AA | 0-0 | 24-21-41 | D42120P | | 3 | | D40258P | | 7 | | 001-099 |
| 3001Y | 18 | | GC | AA | 0-0 | 24-21-41 | D41644P | | 7 | | D40258J | | 7 | | 115-199 |
| 4001B | 20 | | GD | AC | 116-0 | 24-21-41 | D42120P | | 5 | | D40258P | | 10 | | 001-099 |
| 4001B | 20 | | GD | AC | 117-0 | 24-21-41 | D41644P | | 10 | | D40258J | | 10 | | 115-199 |
| 4001G | 20 | | GD | AC | 0-0 | 24-21-41 | D42120P | | 7 | | D40258P | | 11 | | 001-099 |
| 4001G | 20 | | GD | AC | 0-0 | 24-21-41 | D41644P | | 11 | | D40258J | | 11 | | 115-199 |
| 4001R | 20 | | GD | AC | 0-0 | 24-21-41 | D42120P | | 4 | | D40258P | | 12 | | 001-099 |
| 4001R | 20 | | GD | AC | 0-0 | 24-21-41 | D41644P | | 12 | | D40258J | | 12 | | 115-199 |
| 4001Y | 20 | | GD | AC | 0-0 | 24-21-41 | D42120P | | 6 | | D40258P | | 13 | | 001-099 |
| 4001Y | 20 | | GD | AC | 0-0 | 24-21-41 | D41644P | | 13 | | D40258J | | 13 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4010

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|--|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4020 | | 286N4020 | | | E/E BAY TO LEFT MAIN TANK DENSITOMETER CONN. ASSY | | | | | | | | | | | |
| 0001 | | 20 | | GA | | 71-0 | 28-41-21 | D41272P | | 6 | | D06882 | | 6 | | ALL |
| 0002 | | 20 | | GA | | 71-0 | 28-41-21 | D41272P | | 7 | | D06882 | | 7 | | ALL |
| 0003 | | 20 | | GA | | 71-0 | 28-41-21 | D41272P | | 8 | | D06882 | | 8 | | ALL |
| 0004 | | 20 | | GA | | 71-0 | 28-41-21 | D41272P | | 9 | | D06882 | | 9 | | ALL |
| 1001 | | 20 | | W4 | AA | 71-0 | 28-41-21 | D41272P | | 1 | | D06882 | | 1 | | ALL |
| 1001Z | | | | | AA | 0-0 | 28-41-21 | D41272P | | 4 | | D06882 | = C1 | | | ALL |
| 2001B | | 20 | | GB | BA | 71-0 | 28-41-21 | D41272P | | 3 | | D06882 | | 3 | | ALL |
| 2001R | | 20 | | GB | BA | 0-0 | 28-41-21 | D41272P | | 2 | | D06882 | | 2 | | ALL |
| YAAA | | | | | | 0-0 | 28-41-21 | GD00997 | ST.. | GW | | GD02585 | ST.. | GW | | ALL |
| W4022 | | 286N4022 | | | E/E BAY TO RIGHT & CTR MAIN TANK DENSITOMETER CONN. ASSY | | | | | | | | | | | |
| 0001 | | 20 | | GA | | 79-9 | 28-41-31 | D41276P | | 6 | | D06886 | | 6 | | ALL |
| 0002 | | 20 | | GA | | 79-9 | 28-41-31 | D41276P | | 7 | | D06886 | | 7 | | ALL |
| 0003 | | 20 | | GA | | 79-9 | 28-41-31 | D41276P | | 8 | | D06886 | | 8 | | ALL |
| 0004 | | 20 | | GA | | 79-9 | 28-41-31 | D41276P | | 9 | | D06886 | | 9 | | ALL |
| 0005 | | 20 | | GA | | 72-6 | 28-41-41 | D41276P | | 16 | | D11720 | | 12 | | ALL |
| 0006 | | 20 | | GA | | 72-6 | 28-41-41 | D41276P | | 17 | | D11720 | | 13 | | ALL |
| 0007 | | 20 | | GA | | 72-6 | 28-41-41 | D41276P | | 18 | | D11720 | | 14 | | ALL |
| 0008 | | 20 | | GA | | 72-6 | 28-41-41 | D41276P | | 19 | | D11720 | | 5 | | ALL |
| 1001 | | 20 | | W4 | AA | 79-9 | 28-41-31 | D41276P | | 1 | | D06886 | | 1 | | ALL |
| 1001Z | | | | | AA | 0-0 | 28-41-31 | D41276P | | 4 | | D06886 | = C1 | | | ALL |
| 1002 | | 20 | | W4 | AB | 72-6 | 28-41-41 | D41276P | | 11 | | D11720 | | 1 | | ALL |
| 1002Z | | | | | AB | 0-0 | 28-41-41 | D41276P | | 14 | | D11720 | | | AA | ALL |
| 2001B | | 20 | | GB | BA | 79-9 | 28-41-31 | D41276P | | 3 | | D06886 | | 3 | | ALL |
| 2001R | | 20 | | GB | BA | 0-0 | 28-41-31 | D41276P | | 2 | | D06886 | | 2 | | ALL |
| 2002B | | 20 | | GB | BB | 72-6 | 28-41-41 | D41276P | | 13 | | D11720 | | 11 | | ALL |
| 2002R | | 20 | | GB | BB | 0-0 | 28-41-41 | D41276P | | 12 | | D11720 | | 15 | | ALL |
| FRAA | | | | | | 0-0 | 28-41-41 | D11720 | | 3 | | D11720 | | | AA | ALL |
| FRAB | | | | | | 0-0 | 28-41-41 | D11720 | | 8 | | D11720 | | | AA | ALL |
| YAAA | | | | | | 0-0 | 28-41-31 | GD02540 | ST.. | GW | | GD00428 | ST.. | GW | | ALL |
| YAAB | | | | | | 0-0 | 28-41-41 | GD02540 | ST.. | GW | | GD00991 | ST.. | GW | | ALL |
| W4024 | | 286N4024 | | | E/E BAY TO LEFT & CENTER TANK (HI Z & LO Z) ROLLS ROYCE ENG. | | | | | | | | | | | |
| 0001 | | 18 | | GA | | 0-10 | 28-41-21 | D42220P | CAP | Y | | D42220P | | 2 | | 001-099 |
| 0002 | | 18 | | GA | | 0-10 | 28-41-21 | D42220P | CAP | Y | | D42220P | | 3 | | 001-099 |
| 0003 | | 18 | | GA | | 1-0 | 28-41-41 | D42224P | | 2 | | D42224P | CAP | Y | | 001-099 |
| 0004 | | 18 | | GA | | 1-0 | 28-41-41 | D42224P | | 3 | | D42224P | CAP | Y | | 001-099 |
| 001TI | | | | | AA | 0-0 | 28-41-21 | D42220P | = C1 | | | D06880 | = C1 | | | 001-099 |
| 001TO | | | | | AA | 0-0 | 28-41-21 | D42220P | S/R | | | GD02045 | ST.. | GW | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4020

Page 1

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W4020
Page 2
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4026 | 286N4026 | | | E/E BAY TO RIGHT & CENTER TANK (HI Z & LO Z) (continued) | | | | | | | | | | | |
| 001TI | | | | AA | 0-0 | 28-41-31 | D42222P | = C1 | | | D06884 | = C1 | | | 001-099 |
| 001TO | | | | AA | 0-0 | 28-41-31 | D42222P | S/R | | | GD02145 | ST.. | GW | | 001-099 |
| 001TX | 18 | TK | | AA | 79-0 | 28-41-31 | D42222P | 1 | | | D06884 | 1 | | | 001-002 |
| 001TX | 18 | TK | | AA | 79-7 | 28-41-31 | D42222P | 1 | | | D06884 | 1 | | | 003-099 |
| 002TI | | | | AC | 0-0 | 28-41-41 | D42226P | = C1 | | | D06888 | = C1 | | | 001-099 |
| 002TO | | | | AC | 0-0 | 28-41-41 | D42226P | S/R | | | GD00336 | ST.. | GW | | 001-099 |
| 002TX | 18 | TK | | AC | 55-0 | 28-41-41 | D42226P | 1 | | | D06888 | 1 | | | 001-002 |
| 002TX | 18 | TK | | AC | 56-4 | 28-41-41 | D42226P | 1 | | | D06888 | 1 | | | 003-099 |
| 4501AA | 20 | 4K | | DA | 80-0 | 28-41-31 | D41270P | 15 | | | D06884 | 15 | | | 001-002 |
| 4501AA | 20 | 4K | | DA | 79-10 | 28-41-31 | D41270P | 15 | | | D06884 | 15 | | | 003-099 |
| 4501RB | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 6 | | | D06884 | 6 | | | 001-099 |
| 4501RG | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 5 | | | D06884 | 5 | | | 001-099 |
| 4501RK | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 4 | | | D06884 | 4 | | | 001-099 |
| 4501RV | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 8 | | | D06884 | 8 | | | 001-099 |
| 4501RY | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 3 | | | D06884 | 3 | | | 001-099 |
| 4501W | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 17 | | | D06884 | 17 | | | 001-099 |
| 4501WB | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 14 | | | D06884 | 14 | | | 001-099 |
| 4501WG | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 13 | | | D06884 | 13 | | | 001-099 |
| 4501WK | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 7 | | | D06884 | 7 | | | 001-099 |
| 4501WN | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 9 | | | D06884 | 9 | | | 001-099 |
| 4501WO | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 12 | | | D06884 | 12 | | | 001-099 |
| 4501WR | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 10 | | | D06884 | 10 | | | 001-099 |
| 4501WV | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 16 | | | D06884 | 16 | | | 001-099 |
| 4501WY | 20 | 4K | | DA | 0-0 | 28-41-31 | D41270P | 11 | | | D06884 | 11 | | | 001-099 |
| 4501Z | | | | DA | 0-0 | 28-41-31 | D41270P | S/R | | | GD02145 | ST.. | GW | | 001-099 |
| 4502B | 20 | 4L | | DB | 56-0 | 28-41-41 | D42226P | 6 | | | D06888 | 6 | | | 001-002 |
| 4502B | 20 | 4L | | DB | 56-4 | 28-41-41 | D42226P | 6 | | | D06888 | 6 | | | 003-099 |
| 4502G | 20 | 4L | | DB | 0-0 | 28-41-41 | D42226P | 4 | | | D06888 | 4 | | | 001-099 |
| 4502K | 20 | 4L | | DB | 0-0 | 28-41-41 | D42226P | 9 | | | D06888 | 9 | | | 001-099 |
| 4502R | 20 | 4L | | DB | 0-0 | 28-41-41 | D42226P | 5 | | | D06888 | 5 | | | 001-099 |
| 4502Y | 20 | 4L | | DB | 0-0 | 28-41-41 | D42226P | 7 | | | D06888 | 3 | | | 001-099 |
| 4502Z | | | | DB | 0-0 | 28-41-41 | D42226P | S/R | | | GD00336 | ST.. | GW | | 001-099 |
| YAAA | | | | | 0-0 | 28-41-31 | GD01831 | ST.. | GW | | GD03086 | ST.. | GW | | 001-099 |
| YAAB | | | | | 0-0 | 28-41-31 | GD01831 | ST.. | GW | | GD00336 | ST.. | GW | | 001-002 |
| YAAB | | | | | 0-0 | 28-41-41 | GD01831 | ST.. | GW | | GD00336 | ST.. | GW | | 003-099 |
| W4028 | 286N4028 | | | THRUST REVERSER CONTROL SYNCH LOCK LEFT ENGINE P36 TO WING BREAK/P10 | | | | | | | | | | | |
| 0004 | 20 | GA | | | 2-0 | 78-36-11 | GD04058 | DC.. | 2 | | D07688 | 12 | | | 001-002, 115-199 |
| 0004 | 20 | GA | | | 3-0 | 78-36-11 | GD04058 | DC.. | 2 | | D07688 | 12 | | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W4020

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4028 | 286N4028 | | | THRUST REVERSER CONTROL SYNCH LOCK LEFT ENGINE P36 TO WING BREAK/P10 (continued) | | | | | | | | | | | |
| 0005 | 20 | | GA | | 2-0 | 78-36-11 | GD04058 | ST.. | 2 | | D07688 | 11 | | | 001-002, 115-199 |
| 0005 | 20 | | GA | | 3-0 | 78-36-11 | GD04058 | ST.. | 2 | | D07688 | 11 | | | 003-099 |
| 0006 | 20 | | GA | | 2-0 | 78-36-11 | GD04058 | ST.. | 2 | | D07688 | | | AV | 001-002, 115-199 |
| 0006 | 20 | | GA | | 3-0 | 78-36-11 | GD04058 | ST.. | 2 | | D07688 | | | AV | 003-099 |
| 0007 | 20 | | GA | | 2-0 | 78-36-11 | GD04058 | ST.. | 2 | | D07688 | 2 | | | 001-002, 115-199 |
| 0007 | 20 | | GA | | 3-0 | 78-36-11 | GD04058 | ST.. | 2 | | D07688 | 2 | | | 003-099 |
| 0008 | 16 | | GA | | 11-0 | 78-34-51 | D41462P | | 19 | 16 | SP01944 | | 9 | | ALL |
| 0012 | 22 | | GA | | 36-1 | SPARE | D41462P | | 21 | | D07688 | CAP | Y | | 001-002, 115-199 |
| 0012 | 22 | | GA | | 37-0 | SPARE | D41462P | | 21 | | D07688 | CAP | Y | | 003-099 |
| 1002 | 20 | | GT | AN | 36-1 | 78-34-11 | D07688 | | 5 | | D41462P | 31 | | | 001-002, 115-199 |
| 1002 | 18 | | GT | AN | 37-0 | 78-34-11 | D07688 | | 5 | 18 | D41462P | 31 | 18 | | 003-099 |
| 1002Z | | | | AN | 0-0 | 78-34-11 | D07688 | | 1 | | D41462P | | | AA | ALL |
| 1004 | 20 | | GT | AP | 36-1 | 78-34-11 | D07688 | | 8 | | D41462P | 17 | | | 001-002, 115-199 |
| 1004 | 18 | | GT | AP | 37-0 | 78-34-11 | D07688 | | 8 | 18 | D41462P | 17 | 18 | | 003-099 |
| 1004Z | | | | AP | 0-0 | 78-34-11 | D07688 | | 9 | | D41462P | | | AA | ALL |
| 1005 | 22 | | GT | AR | 36-1 | 78-36-11 | D07688 | | 3 | | D41462P | 22 | | | 001-002, 115-199 |
| 1005 | 22 | | GT | AR | 37-0 | 78-36-11 | D07688 | | 3 | | D41462P | 22 | | | 003-099 |
| 1005Z | | | | AR | 0-0 | 78-36-11 | D07688 | | | | D41462P | DED | | | ALL |
| 2501B | 16 | | GF | AF | 63-1 | 78-34-51 | D41462P | | 8 | 16 | D41448J | 4 | | | 001-002, 115-199 |
| 2501B | 16 | | GF | AF | 67-0 | 78-34-51 | D41462P | | 8 | 16 | D41448J | 4 | | | 003-099 |
| 2501R | 16 | | GF | AF | 0-0 | 78-34-51 | D41462P | | 7 | 16 | D41448J | 3 | | | ALL |
| 2501Z | | | | AF | 0-0 | 78-34-51 | D41462P | | 6 | | D41448J | 5 | | | ALL |
| FRAA | | | | | 0-0 | 78-34-11 | D41462P | | 18 | | D41462P | | | AA | ALL |
| FRAV | | | | | 0-0 | 78-36-11 | D07688 | | 4 | | D07688 | | | AV | ALL |
| YAAA | | | | | 0-0 | 78-34-51 | GD03003 | ST.. | E | | D41448J | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4020

Page 4 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----------|---|-------------|------|----------|---------|-------|------|------|-------------|--------|-------|------|------|--------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| I | W4030 | 286N4030 | M11872 HOT SHORT PROTECTOR TO CENTER TANK DENSITOMETER ASSY | | | | | | | | | | | | | |
| I | 6009 | 22 | HA | | 0-7 | 28-41-41 | D11718 | | 2 | | D11718 | CAP | Y | | ALL | |
| I | 6010 | 22 | HA | | 0-7 | 28-41-41 | D11718 | | 4 | | D11718 | CAP | Y | | ALL | |
| I | 6011 | 22 | HA | | 0-7 | 28-41-41 | D11718 | | 6 | | D11718 | CAP | Y | | ALL | |
| I | 6012 | 22 | HA | | 0-7 | 28-41-41 | D11718 | | 7 | | D11718 | CAP | Y | | ALL | |
| I | 6013 | 22 | HA | | 0-7 | 28-41-41 | D11718 | | 9 | | D11718 | CAP | Y | | ALL | |
| I | 6014 | 22 | HA | | 0-7 | 28-41-41 | D11718 | | 10 | | D11718 | CAP | Y | | ALL | |
| I | 8991B | 22 | TM | 1A | 2-9 | 28-41-41 | D11718 | | 11 | | D06890 | | 3 | | ALL | |
| I | 8991H | 22 | TM | 1B | 0-0 | 28-41-41 | D11718 | | 1 | | D06890 | | 1 | | ALL | |
| I | 8991R | 22 | TM | 1A | 0-0 | 28-41-41 | D11718 | | 15 | | D06890 | | 2 | | ALL | |
| I | 8991RB | 22 | TM | 1A | 0-0 | 28-41-41 | D11718 | | 12 | | D06890 | | 6 | | ALL | |
| I | 8991RG | 22 | TM | 1A | 0-0 | 28-41-41 | D11718 | | 13 | | D06890 | | 7 | | ALL | |
| I | 8991RV | 22 | TM | 1A | 0-0 | 28-41-41 | D11718 | | 14 | | D06890 | | 8 | | ALL | |
| I | 8991RY | 22 | TM | 1A | 0-0 | 28-41-41 | D11718 | | 5 | | D06890 | | 9 | | ALL | |
| I | 8991Z | | | 1A | 0-0 | 28-41-41 | D11718 | PERB | | | GD02403 | ST.. | E | | ALL | |
| I | 8991ZA | | | 1B | 0-0 | 28-41-41 | D11718 | | | EE | D06890 | = C1 | | | ALL | |
| I | FRED | | | | 0-0 | 28-41-41 | D11718 | | | EE | D11718 | | 8 | | ALL | |
| I | FREE | | | | 0-0 | 28-41-41 | D11718 | | | EE | D11718 | | 3 | | ALL | |
| I | YAAA | | | | 0-0 | 28-41-41 | D11718 | PERB | | | GD02403 | ST.. | E | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W4030

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|--------|------|------|--------|---------|------|-------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4041 | 286N4041 | | | | LEFT XMTR RAD ALTM (LRRA) ANTENNA | | | | | | | | | | | |
| 002CO | | | | AA | 0-0 | 34-33-11 | D00213 | | = C1 | | D00211B | | = C71 | | ALL | |
| 002CX | | 65 | | AA | 15-11 | 34-33-11 | D00213 | | = A1 | | D00211B | | 71 | 5E | ALL | |
| W4043 | 286N4043 | | | | LEFT RCVR RAD ALTM (LRRA) ANTENNA | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-33-11 | D00215 | | = C1 | | D00211A | | = C71 | | ALL | |
| 001CX | | 65 | | AA | 17-3 | 34-33-11 | D00215 | | = A1 | | D00211A | | 71 | 5E | ALL | |
| W4045 | 286N4045 | | | | RIGHT XMTR RAD ALTM (LRRA) ANTENNA | | | | | | | | | | | |
| 002CO | | | | AA | 0-0 | 34-33-21 | D00219 | | = C1 | | D00217B | | = C71 | | ALL | |
| 002CX | | 65 | | AA | 15-11 | 34-33-21 | D00219 | | = A1 | | D00217B | | 71 | 5E | ALL | |
| W4047 | 286N4047 | | | | RIGHT RCVR RAD ALTM (LRRA) ANTENNA | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-33-21 | D00221 | | = C1 | | D00217A | | = C71 | | ALL | |
| 001CX | | 65 | | AA | 17-3 | 34-33-21 | D00221 | | = A1 | | D00217A | | 71 | 5E | ALL | |
| W4049 | 286N4049 | | | | CENTER XMTR RAD ALTM (LRRA) ANTENNA | | | | | | | | | | | |
| 002CO | | | | AA | 0-0 | 34-33-31 | D00225 | | = C1 | | D00223B | | = C71 | | ALL | |
| 002CX | | 65 | | AA | 15-11 | 34-33-31 | D00225 | | = A1 | | D00223B | | 71 | 5E | ALL | |

WIRE LIST

D280N032

91-21-11

Section W4040

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|---|------------------------|------------------------|-----------------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W4051 | 286N4051 | CENTER RCVR RAD ALTM (LRRRA) ANTENNA | | | |
| 001CO | | AA 0-0 34-33-31 | D00227 = C1 | D00223A = C71 | ALL |
| 001CX | 65 | AA 17-3 34-33-31 | D00227 = A1 | D00223A 71 5E | ALL |
| W4053 | 286N4053 | LEFT DME ANTENNA TO E/E BAY | | | |
| 001CO | | AA 0-0 34-55-11 | D00237 = C1 | D42145P = C1 | ALL |
| 001CX | JB | AA 25-0 34-55-11 | D00237 = A1 | D42145P = A1 | ALL |
| W4055 | 286N4055 | RIGHT DME (STA 972 TO E/E BAY) | | | |
| 001CO | | AA 0-0 34-55-21 | D00241 = C1 | D42147P = C1 | ALL |
| 001CX | JB | AA 23-0 34-55-21 | D00241 = A1 | D42147P = A1 | ALL |
| W4057 | 286N4057 | E4-4 SHELF TO RIGHT SIDEWALL. | | | |
| 0001 | 22 | GA 35-0 23-34-12 | D41547J 6 | D00481 F | 001-003, 005, 007-099 |
| 0001 | 22 | GA 33-0 23-34-12 | D41547J 6 | D00481 F | 004, 006 |
| 0001 | 22 | GA 41-0 23-34-12 | D41547J 6 | D00481 F | 115-199 |
| 0002 | 22 | GA 122-0 23-34-12 | D41547J 12 | D01371 F | 001-003, 005, 007-099 |
| 0002 | 22 | GA 123-0 23-34-12 | D41547J 12 | D01371 F | 004, 006 |
| 0002 | 22 | GA 101-0 23-34-12 | D41547J 12 | D01371 F | 115-199 |
| 0003 | 20 | GA 1-0 23-34-12 | SM00001 9 | D00481 D | 001-099 |
| 0004 | 20 | GA 1-0 23-34-12 | SM00002 9 | D00481 E | 001-099 |
| 0005 | 20 | GA 1-0 23-34-12 | SM00003 9 | D01371 D | 001-099 |
| 0006 | 20 | GA 1-0 23-34-12 | SM00004 9 | D01371 E | 001-099 |
| 2001B | 18 | GB AA 35-0 23-34-12 | D41547J 5 18 | SM00002 9 | 001-003, 005, 007-099 |
| 2001B | 18 | GB AA 32-0 23-34-12 | D41547J 5 18 | SM00002 9 | 004, 006 |
| 2001B | 20 | GB AA 41-0 23-34-12 | D41547J 5 | D00481 E | 115-199 |
| 2001R | 18 | GB AA 0-0 23-34-12 | D41547J 15 18 | SM00001 9 | 001-099 |
| 2001R | 20 | GB AA 0-0 23-34-12 | D41547J 4 | D00481 D | 115-199 |
| 2002B | 18 | GB AB 122-0 23-34-12 | D41547J 13 18 | SM00004 9 | 001-099 |
| 2002B | 20 | GB AB 101-0 23-34-12 | D41547J 11 | D01371 E | 115-199 |
| 2002R | 18 | GB AB 0-0 23-34-12 | D41547J 10 18 | SM00003 9 | 001-099 |
| 2002R | 20 | GB AB 0-0 23-34-12 | D41547J 10 | D01371 D | 115-199 |
| 5001B | 24 | W9 AC 35-0 23-34-12 | D41547J 2 | D00481 B | 001-003, 005, 007-099 |
| 5001B | 24 | W9 AC 33-0 23-34-12 | D41547J 2 | D00481 B | 004, 006 |
| 5001B | 24 | W9 AC 41-0 23-34-12 | D41547J 2 | D00481 B | 115-199 |
| 5001W | 24 | W9 AC 0-0 23-34-12 | D41547J 3 | D00481 A | ALL |
| 5001Z | | AC 0-0 23-34-12 | D41547J 1 | D00481 C | ALL |
| 5002B | 24 | W9 AD 122-0 23-34-12 | D41547J 8 | D01371 B | 001-003, 005, 007-099 |
| 5002B | 24 | W9 AD 123-0 23-34-12 | D41547J 8 | D01371 B | 004, 006 |

WIRE LIST

D280N032

91-21-11

Section W4050

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4057 | 286N4057 | | | E4-4 SHELF TO RIGHT SIDEWALL. (continued) | | | | | | | | | | | |
| 5002B | 24 | | W9 | AD | 101-0 | 23-34-12 | D41547J | | | 8 | D01371 | | B | | 115-199 |
| 5002W | 24 | | W9 | AD | 0-0 | 23-34-12 | D41547J | | | 9 | D01371 | | A | | ALL |
| 5002Z | | | | AD | 0-0 | 23-34-12 | D41547J | | | 7 | D01371 | | C | | ALL |
| W4059 | 286N4059 | | | E4-4 SHELF TO LEFT SIDEWALL. | | | | | | | | | | | |
| 0001 | 22 | | GA | | 38-0 | 23-34-12 | D41549J | | | 6 | D00483 | | F | | 001-099 |
| 0001 | 22 | | GA | | 39-0 | 23-34-12 | D41549J | | | 6 | D00483 | | F | | 115-199 |
| 0002 | 22 | | GA | | 155-0 | 23-34-12 | D41549J | | | 12 | D01369 | | F | | 001-099 |
| 0002 | 22 | | GA | | 107-0 | 23-34-12 | D41549J | | | 12 | D01369 | | F | | 115-199 |
| 0003 | 20 | | GA | | 1-0 | 23-34-12 | SM00001 | | 9 | | D00483 | | D | | 001-099 |
| 0004 | 20 | | GA | | 1-0 | 23-34-12 | SM00002 | | 9 | | D00483 | | E | | 001-099 |
| 0005 | 20 | | GA | | 1-0 | 23-34-12 | SM00003 | | 9 | | D01369 | | D | | 001-099 |
| 0006 | 20 | | GA | | 1-0 | 23-34-12 | SM00004 | | 9 | | D01369 | | E | | 001-099 |
| 2001B | 18 | | GB | AA | 37-0 | 23-34-12 | D41549J | | 5 | 18 | SM00002 | | | 9 | 001-099 |
| 2001B | 20 | | GB | AA | 37-0 | 23-34-12 | D41549J | | 5 | | D00483 | | E | | 115-199 |
| 2001R | 18 | | GB | AA | 0-0 | 23-34-12 | D41549J | | 15 | 18 | SM00001 | | | 9 | 001-099 |
| 2001R | 20 | | GB | AA | 0-0 | 23-34-12 | D41549J | | 4 | | D00483 | | D | | 115-199 |
| 2002B | 18 | | GB | AB | 154-0 | 23-34-12 | D41549J | | 13 | 18 | SM00004 | | | 9 | 001-099 |
| 2002B | 20 | | GB | AB | 106-0 | 23-34-12 | D41549J | | 11 | | D01369 | | E | | 115-199 |
| 2002R | 18 | | GB | AB | 0-0 | 23-34-12 | D41549J | | 10 | 18 | SM00003 | | | 9 | 001-099 |
| 2002R | 20 | | GB | AB | 0-0 | 23-34-12 | D41549J | | 10 | | D01369 | | D | | 115-199 |
| 5001B | 24 | | W9 | AC | 38-0 | 23-34-12 | D41549J | | 2 | | D00483 | | B | | 001-099 |
| 5001B | 24 | | W9 | AC | 39-0 | 23-34-12 | D41549J | | 2 | | D00483 | | B | | 115-199 |
| 5001W | 24 | | W9 | AC | 0-0 | 23-34-12 | D41549J | | 3 | | D00483 | | A | | ALL |
| 5001Z | | | | AC | 0-0 | 23-34-12 | D41549J | | 1 | | D00483 | | C | | ALL |
| 5002B | 24 | | W9 | AD | 130-0 | 23-34-12 | D41549J | | 8 | | D01369 | | B | | 001-099 |
| 5002B | 24 | | W9 | AD | 107-0 | 23-34-12 | D41549J | | 8 | | D01369 | | B | | 115-199 |
| 5002W | 24 | | W9 | AD | 0-0 | 23-34-12 | D41549J | | 9 | | D01369 | | A | | ALL |
| 5002Z | | | | AD | 0-0 | 23-34-12 | D41549J | | 7 | | D01369 | | C | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4050

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4061 | 286N4061 | | | E4-3 SHELF TO E6 SHELF | | | | | | | | | | | |
| 0001 | 24 | | GK | | 143-0 | 23-51-14 | D41687P | | 9 | | D42207P | | 9 | | 115-199 |
| 0002 | 22 | | GA | | 144-0 | 34-51-21 | D41829P | | 7 | | D41683P | | 19 | | 115-199 |
| 0003 | 24 | | GK | | 144-0 | 34-51-21 | D41829P | | 11 | | D41683P | | 29 | | 115-199 |
| 0004 | 20 | | GA | | 143-0 | 23-51-14 | D41687P | | 22 | | D42207P | | 10 | | 115-199 |
| 2001B | 24 | | GL | AA | 143-0 | 23-21-11 | D42207P | | 2 | | D41687P | | 2 | | 115-199 |
| 2001R | 24 | | GL | AA | 0-0 | 23-21-11 | D42207P | | 1 | | D41687P | | 1 | | 115-199 |
| 2501B | 24 | | G2 | AB | 142-0 | 23-51-12 | D41687P | | 3 | | D41683P | | 3 | | 115-199 |
| 2501R | 24 | | G2 | AB | 0-0 | 23-51-12 | D41683P | | 4 | | D41687P | | 4 | | 115-199 |
| 2501Z | | | | AB | 0-0 | 23-51-12 | D41683P | | 5 | | D41687P | | 5 | | 115-199 |
| 2502B | 24 | | G2 | AC | 142-0 | 23-51-13 | D41683P | | 40 | | D41687P | | 6 | | 115-199 |
| 2502R | 24 | | G2 | AC | 0-0 | 23-51-13 | D41683P | | 39 | | D41687P | | 7 | | 115-199 |
| 2502Z | | | | AC | 0-0 | 23-51-13 | D41683P | | 38 | | D41687P | | 8 | | 115-199 |
| 2503B | 24 | | G2 | AD | 143-0 | 23-51-14 | D41687P | | 13 | | D42207P | | 6 | | 115-199 |
| 2503R | 24 | | G2 | AD | 0-0 | 23-51-14 | D41687P | | 14 | | D42207P | | 7 | | 115-199 |
| 2503Z | | | | AD | 0-0 | 23-51-14 | D41687P | | 15 | | D42207P | | 8 | | 115-199 |
| 2504B | 24 | | G2 | AE | 143-0 | 23-51-14 | D41687P | | 16 | | D42207P | | 3 | | 115-199 |
| 2504R | 24 | | G2 | AE | 0-0 | 23-51-14 | D41687P | | 17 | | D42207P | | 4 | | 115-199 |
| 2504Z | | | | AE | 0-0 | 23-51-14 | D41687P | | 18 | | D42207P | | 5 | | 115-199 |
| 5001B | 24 | | G2 | AF | 144-0 | 34-51-21 | D41829P | | 2 | | D41683P | | 14 | | 115-199 |
| 5001R | 24 | | G2 | AF | 0-0 | 34-51-21 | D41829P | | 1 | | D41683P | | 13 | | 115-199 |
| 5001Z | | | | AF | 0-0 | 34-51-21 | D41829P | | 3 | | D41683P | | 15 | | 115-199 |
| 5002B | 24 | | G2 | AG | 144-0 | 34-51-21 | D41829P | | 5 | | D41683P | | 17 | | 115-199 |
| 5002R | 24 | | G2 | AG | 0-0 | 34-51-21 | D41829P | | 4 | | D41683P | | 16 | | 115-199 |
| 5002Z | | | | AG | 0-0 | 34-51-21 | D41829P | | 6 | | D41683P | | 18 | | 115-199 |
| 5004B | 24 | | G2 | AI | 144-0 | 34-22-29 | D41829P | | 13 | | D41683P | | 31 | | 115-199 |
| 5004R | 24 | | G2 | AI | 0-0 | 34-22-29 | D41829P | | 12 | | D41683P | | 30 | | 115-199 |
| 5004Z | | | | AI | 0-0 | 34-22-29 | D41829P | | 14 | | D41683P | | 32 | | 115-199 |
| 5094B | 24 | | G2 | HH | 144-0 | 34-22-28 | D41829P | | 9 | | D41683P | | 9 | | 115-199 |
| 5094R | 24 | | G2 | HH | 0-0 | 34-22-28 | D41829P | | 8 | | D41683P | | 8 | | 115-199 |
| 5094Z | | | | HH | 0-0 | 34-22-28 | D41829P | | 10 | | D41683P | | 10 | | 115-199 |
| W4063 | 286N4063 | | | E4-3 SHELF TO E6 SHELF | | | | | | | | | | | |
| 0001 | 24 | | GK | | 138-0 | 23-51-14 | D42211P | | 9 | | D41689P | | 3 | | 115-199 |
| 0002 | 24 | | GK | | 145-0 | 34-51-11 | D41831P | | 1 | | D41685P | | 23 | | 115-199 |
| 0003 | 22 | | GA | | 145-0 | 34-51-11 | D41831P | | 5 | | D41685P | | 32 | | 115-199 |
| 0004 | 20 | | GA | | 138-0 | 23-51-14 | D41689P | | 22 | | D42211P | | 10 | | 115-199 |
| 2001B | 24 | | GL | AA | 138-0 | 23-21-11 | D42211P | | 1 | | D41689P | | 1 | | 115-199 |
| 2001R | 24 | | GL | AA | 0-0 | 23-21-11 | D42211P | | 2 | | D41689P | | 2 | | 115-199 |
| 2501B | 24 | | G2 | AB | 136-0 | 23-51-12 | D41685P | | 4 | | D41689P | | 4 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4060

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|------------------------------------|----------|---------|------|------|--------|-------|------|---------|--------|-------------|--|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4063 | 286N4063 | | | | E4-3 SHELF TO E6 SHELF (continued) | | | | | | | | | | | | |
| 2501R | 24 | | G2 | AB | 0-0 | 23-51-12 | D41685P | | | | 5 | | D41689P | 5 | | | 115-199 |
| 2501Z | | | | AB | 0-0 | 23-51-12 | D41685P | | | | 6 | | D41689P | 6 | | | 115-199 |
| 2502B | 24 | | G2 | AC | 136-0 | 23-51-12 | D41685P | | | | 7 | | D41689P | 7 | | | 115-199 |
| 2502R | 24 | | G2 | AC | 0-0 | 23-51-12 | D41685P | | | | 8 | | D41689P | 8 | | | 115-199 |
| 2502Z | | | | AC | 0-0 | 23-51-12 | D41685P | | | | 9 | | D41689P | 9 | | | 115-199 |
| 2503B | 24 | | G2 | AD | 136-0 | 23-51-13 | D41685P | | | | 10 | | D41689P | 10 | | | 115-199 |
| 2503R | 24 | | G2 | AD | 0-0 | 23-51-13 | D41685P | | | | 11 | | D41689P | 11 | | | 115-199 |
| 2503Z | | | | AD | 0-0 | 23-51-13 | D41685P | | | | 12 | | D41689P | 12 | | | 115-199 |
| 2504B | 24 | | G2 | AE | 138-0 | 23-51-14 | D42211P | | | | 6 | | D41689P | 13 | | | 115-199 |
| 2504R | 24 | | G2 | AE | 0-0 | 23-51-14 | D42211P | | | | 7 | | D41689P | 14 | | | 115-199 |
| 2504Z | | | | AE | 0-0 | 23-51-14 | D42211P | | | | 8 | | D41689P | 15 | | | 115-199 |
| 2505B | 24 | | G2 | AF | 138-0 | 23-51-14 | D42211P | | | | 3 | | D41689P | 16 | | | 115-199 |
| 2505R | 24 | | G2 | AF | 0-0 | 23-51-14 | D42211P | | | | 4 | | D41689P | 17 | | | 115-199 |
| 2505Z | | | | AF | 0-0 | 23-51-14 | D42211P | | | | 5 | | D41689P | 18 | | | 115-199 |
| 5001B | 24 | | G2 | AG | 145-0 | 34-51-11 | D41831P | | | | 3 | | D41685P | 30 | | | 115-199 |
| 5001R | 24 | | G2 | AG | 0-0 | 34-51-11 | D41831P | | | | 2 | | D41685P | 29 | | | 115-199 |
| 5001Z | | | | AG | 0-0 | 34-51-11 | D41831P | | | | 4 | | D41685P | 31 | | | 115-199 |
| 5002B | 24 | | G2 | AH | 145-0 | 34-51-11 | D41831P | | | | 7 | | D41685P | 34 | | | 115-199 |
| 5002R | 24 | | G2 | AH | 0-0 | 34-51-11 | D41831P | | | | 6 | | D41685P | 33 | | | 115-199 |
| 5002Z | | | | AH | 0-0 | 34-51-11 | D41831P | | | | 8 | | D41685P | 35 | | | 115-199 |
| 5003B | 24 | | G2 | AI | 145-0 | 34-22-19 | D41831P | | | | 10 | | D41685P | 42 | | | 115-199 |
| 5003R | 24 | | G2 | AI | 0-0 | 34-22-19 | D41831P | | | | 9 | | D41685P | 41 | | | 115-199 |
| 5003Z | | | | AI | 0-0 | 34-22-19 | D41831P | | | | 11 | | D41685P | 43 | | | 115-199 |
| 5004B | 24 | | G2 | AJ | 136-0 | SPARE | D41685P | | | | 26 | | D41689P | 26 | | | 115-199 |
| 5004R | 24 | | G2 | AJ | 0-0 | SPARE | D41685P | | | | 27 | | D41689P | 27 | | | 115-199 |
| 5004Z | | | | AJ | 0-0 | SPARE | D41685P | | | | 28 | | D41689P | 28 | | | 115-199 |
| 5058B | 24 | | G2 | HH | 143-0 | 34-22-18 | D41831P | | | | 14 | | D41685P | 14 | | | 115-199 |
| 5058R | 24 | | G2 | HH | 0-0 | 34-22-18 | D41831P | | | | 13 | | D41685P | 13 | | | 115-199 |
| 5058Z | | | | HH | 0-0 | 34-22-18 | D41831P | | | | 15 | | D41685P | 15 | | | 115-199 |

WIRE LIST

D280N032

91-21-11
Section W4060
Page 2 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | To | | | | | |
|------------|-------------|----|----|-------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4071 | 286N4071 | | | VHF-L COAX, E4-3 TO ANT | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-12-11 | D41721P | = C1 | | | D00131 | = C1 | | | ALL |
| 001CX | | | | BS AA | 40-0 | 23-12-11 | D41721P | = A1 | | | D00131 | = A1 | | | 001-099 |
| 001CX | | | | 65 AA | 40-0 | 23-12-11 | D41721P | = A1 | | | D00131 | = A1 | | | 115-199 |
| W4073 | 286N4073 | | | VHF-R COAX, E4-3 TO ANT | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 23-12-21 | D00133 | = C1 | | | D41731P | = C1 | | | ALL |
| 001CX | | | | BS AA | 23-0 | 23-12-21 | D00133 | = A1 | | | D41731P | = A1 | | | 001-099 |
| 001CX | | | | 65 AA | 25-0 | 23-12-21 | D00133 | = A1 | | | D41731P | = A1 | | | 115-199 |
| W4079 | 286N4079 | | | GPS ANT-L (COAX) | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-58-11 | D45017P | = C1 | | | D02003 | = C1 | | | 115-199 |
| 001CX | | | | 0F AA | 44-3 | 34-58-11 | D45017P | = A1 | | | D02003 | = A1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4070

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|-------------|---------------------------------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4081 | 286N4081 | | | | | GPS ANT-R (COAX) | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-58-21 | D45019P | = C1 | | | D02009 | = C1 | | | 115-199 |
| 001CX | | OF | | AA | 40-5 | 34-58-21 | D45019P | = A1 | | | D02009 | = A1 | | | 115-199 |
| W4086 | 286N4086 | | | | | P37 TO E/E CENTER LIGHTS | | | | | | | | | |
| 0001 | 20 | | GA | | 34-0 | 33-31-41 | D40760P | 1 | | | S00357 | 2 | C | | 115-199 |
| 0002 | 18 | | GA | | 9-0 | 33-31-41 | D40760P | 2 | | | S00355 | 5 | C | * | 115-199 |
| 0003 | 20 | | GA | | 21-0 | 33-31-41 | S00357 | 3 | C | | SP00246 | | 9 | | 115-199 |
| 0004 | 20 | | GA | | 18-0 | 33-31-41 | SP00246 | | 9 | | SP00248 | | 9 | | 115-199 |
| 0005 | 20 | | GA | | 21-0 | 33-31-41 | SP00246 | | 9 | | SP00250 | | 9 | | 115-199 |
| 0006 | 18 | | GA | | 1-0 | 33-31-41 | S00355 | 5 | C | | S00355 | 2 | C | | 001-099 |
| 0006 | 18 | | GA | | 2-0 | 33-31-41 | S00355 | 5 | C | * | S00355 | 2 | C | | 115-199 |
| 0007 | 18 | | GA | | 19-0 | 33-31-41 | S00355 | 6 | C | | SP00226 | | 9 | | ALL |
| 0008 | 18 | | GA | | 16-0 | 33-31-41 | S00355 | 3 | C | | SP00234 | | 9 | | 001-099 |
| 0008 | 18 | | GA | | 18-0 | 33-31-41 | S00355 | 3 | C | | SP00234 | | 9 | | 115-199 |
| 0009 | 18 | | GA | | 11-0 | 33-31-41 | SP00226 | | 9 | | SP00228 | | 9 | | 001-099 |
| 0009 | 18 | | GA | | 12-0 | 33-31-41 | SP00226 | | 9 | | SP00228 | | 9 | | 115-199 |
| 0010 | 18 | | GA | | 7-0 | 33-31-41 | SP00228 | | 9 | | SP00230 | | 9 | | 001-099 |
| 0010 | 18 | | GA | | 5-0 | 33-31-41 | SP00228 | | 9 | | SP00230 | | 9 | | 115-199 |
| 0011 | 18 | | GA | | 7-0 | 33-31-41 | SP00230 | | 9 | | SP00232 | | 9 | | ALL |
| 0012 | 18 | | GA | | 11-0 | 33-31-41 | SP00234 | | 9 | | SP00236 | | 9 | | ALL |
| 0014 | 18 | | GA | | 8-0 | 33-31-41 | SP00234 | | 9 | | SP00238 | | 9 | | 001-099 |
| 0014 | 18 | | GA | | 6-0 | 33-31-41 | SP00234 | | 9 | | SP00238 | | 9 | | 115-199 |
| 0017 | 18 | | GA | | 9-0 | 25-29-11 | D00878 | = P | D | | D40760P | 3 | | | 115-199 |
| 0018 | 18 | | GA | | 2-0 | 25-29-11 | D00878 | = G | D | | GD02460 | ST.. | E | | 115-199 |
| 0019 | 18 | | GA | | 2-0 | 25-29-11 | D00878 | = N | D | | GD00925 | AC.. | E | | 115-199 |
| A-A | | | | | 0-0 | 33-31-41 | L00337 | = P | | | SP00226 | | 9 | | ALL |
| A-B | | | | | 0-0 | 33-31-41 | L00338 | = P | | | SP00228 | | 9 | | ALL |
| A-C | | | | | 0-0 | 33-31-41 | L00339 | = P | | | SP00230 | | 9 | | ALL |
| A-D | | | | | 0-0 | 33-31-41 | L00340 | = P | | | SP00232 | | 9 | | ALL |
| A-E | | | | | 0-0 | 33-31-41 | L00341 | = P | | | SP00234 | | 9 | | ALL |
| A-F | | | | | 0-0 | 33-31-41 | L00342 | = P | | | SP00236 | | 9 | | ALL |
| A-G | | | | | 0-0 | 33-31-41 | L00343 | = P | | | SP00238 | | 9 | | ALL |
| A-K | | | | | 0-0 | 33-31-41 | L00384 | = P | | | SP00246 | | 9 | | 115-199 |
| A-L | | | | | 0-0 | 33-31-41 | L00335 | = P | | | SP00248 | | 9 | | 115-199 |
| A-M | | | | | 0-0 | 33-31-41 | L00336 | = P | | | SP00250 | | 9 | | 115-199 |
| B-A | | | | | 0-0 | 33-31-41 | L00337 | = G | | | GD00149 | AC.. | E | | ALL |
| B-B | | | | | 0-0 | 33-31-41 | L00338 | = G | | | GD00150 | AC.. | E | | ALL |
| B-C | | | | | 0-0 | 33-31-41 | L00339 | = G | | | GD00151 | AC.. | E | | ALL |
| B-D | | | | | 0-0 | 33-31-41 | L00340 | = G | | | GD00152 | AC.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4080

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|----|--------------------------------------|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4086 | 286N4086 | | | P37 TO E/E CENTER LIGHTS (continued) | | | | | | | | | | | |
| B-E | | | | | 0-0 | 33-31-41 | L00341 | = | G | | GD00153 | AC.. | E | | ALL |
| B-F | | | | | 0-0 | 33-31-41 | L00342 | = | G | | GD00154 | AC.. | E | | ALL |
| B-G | | | | | 0-0 | 33-31-41 | L00343 | = | G | | GD00155 | AC.. | E | | ALL |
| B-K | | | | | 0-0 | 33-31-41 | L00384 | = | G | | GD00159 | AC.. | E | | 115-199 |
| B-L | | | | | 0-0 | 33-31-41 | L00335 | = | G | | GD00160 | AC.. | E | | 115-199 |
| B-M | | | | | 0-0 | 33-31-41 | L00336 | = | G | | GD00161 | AC.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4080

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4104 | 286N4104 | | | RIGHT MIX BAY AND FORWARD CARGO LIGHTS | | | | | | | | | | | |
| 0008 | 16 | | GA | | 26-0 | 21-58-13 | D01628 | | 1 | | D40050P | | 8 | | 001-099 |
| 0008 | 16 | | GA | | 25-0 | 21-58-13 | D01628 | | 1 | | D40050P | | 8 | | 115-199 |
| 0009 | 16 | | GA | | 26-0 | 21-58-13 | D01628 | | 2 | | D40050P | | 9 | | 001-099 |
| 0009 | 16 | | GA | | 25-0 | 21-58-13 | D01628 | | 2 | | D40050P | | 9 | | 115-199 |
| 0010 | 16 | | GA | | 26-0 | 21-58-13 | D01628 | | 3 | | D40050P | | 10 | | 001-099 |
| 0010 | 16 | | GA | | 25-0 | 21-58-13 | D01628 | | 3 | | D40050P | | 10 | | 115-199 |
| 0011 | 16 | | GA | | 26-0 | 21-58-13 | D01628 | | 5 | | D40050P | | 3 | | 001-099 |
| 0011 | 16 | | GA | | 25-0 | 21-58-13 | D40050P | | 3 | | D01628 | | 5 | | 115-199 |
| 0012 | 16 | | GA | | 26-0 | 21-58-13 | D01628 | | 6 | | D40050P | | 4 | | 001-099 |
| 0012 | 16 | | GA | | 25-0 | 21-58-13 | D01628 | | 6 | | D40050P | | 4 | | 115-199 |
| 0013 | 16 | | GA | | 4-0 | 21-58-13 | D01628 | | 7 | | GD00869 | ST.. | E | | 001-099 |
| 0013 | 16 | | GA | | 5-0 | 21-58-13 | D01628 | | 7 | | GD00869 | ST.. | E | | 115-199 |
| 0030 | 14 | | GA | | 51-0 | 21-25-11 | D40050P | | 1 | | D02590 | | 2 | | 001-099 |
| 0030 | 14 | | GA | | 53-0 | 21-25-11 | D40050P | | 1 | | D02590 | | 2 | | 115-199 |
| 0031 | 14 | | GA | | 51-0 | 21-25-11 | D40050P | | 2 | | D02590 | | 3 | | 001-099 |
| 0031 | 14 | | GA | | 53-0 | 21-25-11 | D40050P | | 2 | | D02590 | | 3 | | 115-199 |
| 0032 | 14 | | GA | | 51-0 | 21-25-11 | D40050P | | 11 | | D02590 | | 4 | | 001-099 |
| 0032 | 14 | | GA | | 53-0 | 21-25-11 | D40050P | | 11 | | D02590 | | 4 | | 115-199 |
| 0033 | 14 | | GA | | 5-0 | 21-25-11 | GD02364 | ST.. | E | | D02590 | | 7 | | ALL |
| 0034 | 24 | | GK | | 5-0 | 21-25-11 | D02590 | | 6 | | GD03278 | AC.. | E | | ALL |
| 0035 | 24 | | GK | | 51-0 | 21-25-11 | D40050P | | 12 | | D02590 | | 5 | | 001-099 |
| 0035 | 24 | | GK | | 53-0 | 21-25-11 | D40050P | | 12 | | D02590 | | 5 | | 115-199 |
| 0036 | 20 | | GA | | 15-0 | 52-34-11 | D40080P | | 1 | | D41922J | | 12 | | 001-099 |
| 0036 | 20 | | GA | | 14-0 | 52-34-11 | D40080P | | 1 | | D41922J | | 12 | | 115-199 |
| 0037 | 20 | | GA | | 15-0 | 52-34-11 | D40080P | | 2 | | D41922J | | 13 | | 001-099 |
| 0037 | 20 | | GA | | 14-0 | 52-34-11 | D40080P | | 2 | | D41922J | | 13 | | 115-199 |
| 0038 | 20 | | GA | | 15-0 | 52-34-11 | D40080P | | 3 | | D41922J | | 14 | | 001-099 |
| 0038 | 20 | | GA | | 14-0 | 52-34-11 | D40080P | | 3 | | D41922J | | 14 | | 115-199 |
| 0040 | 22 | | GA | | 25-0 | 52-34-11 | D41928P | | 1 | | D41922J | | 8 | | 001-099 |
| 0040 | 22 | | GA | | 27-0 | 52-34-11 | D41928P | | 1 | | D41922J | | 8 | | 115-199 |
| 0041 | 22 | | GA | | 25-0 | 52-34-11 | D41928P | | 2 | | D41922J | | 7 | | 001-099 |
| 0041 | 22 | | GA | | 27-0 | 52-34-11 | D41928P | | 2 | | D41922J | | 7 | | 115-199 |
| 0042 | 22 | | GA | | 25-0 | 52-34-11 | D41928P | | 3 | | SP01052 | | 9 | | 001-099 |
| 0042 | 22 | | GA | | 30-0 | 52-34-11 | D41928P | | 3 | | SP01052 | | 9 | | 115-199 |
| 0048 | 22 | | GA | | 16-0 | 52-34-11 | S10180 | | 1 | C | SP00182 | | 9 | | ALL |
| 0050 | 22 | | GA | | 16-0 | 52-34-11 | S10180 | | 6 | C | SP00178 | | 9 | | ALL |
| 0051 | 22 | | GA | | 39-0 | 33-37-11 | D40080P | | 5 | | SP00380 | | 9 | | 001-099 |
| 0051 | 18 | | GA | | 41-0 | 33-37-11 | D40080P | | 5 | | SP00380 | | 9 | | 115-199 |
| 0052 | 22 | | GA | | 34-0 | 33-37-11 | D41922J | | 6 | | SP00382 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | Effectivity | | | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|-------------|---------|-------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | | Splice | Equip | Term | Type | Splice |
| W4104 | 286N4104 | | | RIGHT MIX BAY AND FORWARD CARGO LIGHTS (continued) | | | | | | | | | | | | |
| 0052 | 20 | GA | | | 31-0 | 33-37-11 | D41922J | 6 | | | | SP00382 | | 9 | | 115-199 |
| 0068 | 22 | GA | | | 15-0 | SPARE | D40080P | 6 | | | | D41922J | 2 | | | 001-099 |
| 0068 | 22 | GA | | | 14-0 | 25-51-11 | D40080P | 6 | | | | D41922J | 2 | | | 115-199 |
| 0069 | 18 | GA | | | 15-0 | SPARE | D40080P | 7 | | | | D41922J | 9 | | | 001-099 |
| 0069 | 16 | GA | | | 14-0 | 25-51-11 | D40080P | 7 | | | | D41922J | 9 | | | 115-199 |
| 0070 | 18 | GA | | | 15-0 | SPARE | D40080P | 8 | | | | D41922J | 10 | | | 001-099 |
| 0070 | 16 | GA | | | 14-0 | 25-51-11 | D40080P | 8 | | | | D41922J | 10 | | | 115-199 |
| 0071 | 18 | GA | | | 15-0 | SPARE | D40080P | 9 | | | | D41922J | 11 | | | 001-099 |
| 0071 | 16 | GA | | | 14-0 | 25-51-11 | D40080P | 9 | | | | D41922J | 11 | | | 115-199 |
| 0072 | 20 | GA | | | 3-0 | 25-51-11 | D41922J | 4 | | | | GD00133 | DC.. | E | | 115-199 |
| 0073 | 20 | GA | | | 3-0 | 25-51-11 | D41922J | 3 | | | | GD00133 | DC.. | E | | ALL |
| 0074 | 22 | GA | | | 12-0 | 33-37-11 | D41922J | 5 | | | | SP01052 | | 9 | | 001-099 |
| 0074 | 22 | GA | | | 7-0 | 33-37-11 | D41922J | 5 | | | | SP01052 | | 9 | | 115-199 |
| 0077 | 20 | GA | | | 13-0 | 30-71-21 | D40050P | 6 | | | | SP00277 | | 9 | | 001-099 |
| 0079 | 22 | GA | | | 20-0 | 52-34-11 | D40080P | 4 | | | | SP01052 | | 9 | | 001-099 |
| 0079 | 22 | GA | | | 17-0 | 52-34-11 | D40080P | 4 | | | | SP01052 | | 9 | | 115-199 |
| 0080 | 22 | GA | | | 19-0 | 52-34-11 | S10180 | 2 | C | * | | SP01052 | | 9 | | 001-099 |
| 0080 | 22 | GA | | | 23-0 | 52-34-11 | S10180 | 2 | C | | | SP01052 | | 9 | | 115-199 |
| 0081 | 22 | GA | | | 1-0 | 52-34-11 | S10180 | 5 | C | | | S10180 | 2 | C | * | 001-099 |
| 0081 | 22 | GA | | | 23-0 | 52-34-11 | S10180 | 5 | C | | | SP01052 | | 9 | | 115-199 |
| 0082 | 20 | GA | | | 75-0 | 30-71-21 | SP00277 | 9 | | | | SP00285 | | 9 | | 001-099 |
| 0085 | 20 | GA | | | 1-0 | SPARE | SP00285 | 9 | | | | SP00285 | CAP | Y | | 001 |
| 0085 | 20 | GA | | | 1-0 | 30-71-21 | SP00285 | 9 | | | | SP00323 | | 9 | | 002 |
| 0085 | 20 | GA | | | 34-0 | 30-71-21 | SP00285 | 9 | | | | SP00323 | | 9 | | 003-099 |
| 2001B | 22 | GB | BA | | 31-0 | 52-34-11 | D41928P | 5 | | | | SP00086 | | 9 | | 001-099 |
| 2001B | 22 | GB | BA | | 36-0 | 52-34-11 | D41928P | 5 | | | | SP00086 | | 9 | | 115-199 |
| 2001R | 22 | GB | BA | | 0-0 | 52-34-11 | D41928P | 4 | | | | SP00084 | | 9 | | ALL |
| 2003B | 22 | GB | BC | | 29-0 | 52-34-11 | D41928P | 9 | | | | SP00094 | | 9 | | ALL |
| 2003R | 22 | GB | BC | | 0-0 | 52-34-11 | D41928P | 8 | | | | SP00092 | | 9 | | ALL |
| 2005B | 24 | GL | BE | | 31-0 | 52-71-21 | D41928P | 13 | | | | SP00172 | | 9 | | 001-099 |
| 2005B | 24 | GL | BE | | 30-0 | 52-71-21 | D41928P | 13 | | | | SP00172 | | 9 | | 115-199 |
| 2005R | 24 | GL | BE | | 0-0 | 52-71-21 | D41928P | 12 | | | | SP00170 | | 9 | | ALL |
| A-BK | | | | | 0-0 | 30-71-21 | SP00426 | | 9 | | | B00117 | = 1 | | | 001-099 |
| A-BL | | | | | 0-0 | 52-34-11 | SP00086 | | 9 | | | S10350 | BLU | | | 001-099 |
| A-BL | | | AA | | 0-0 | 52-34-11 | SP00086 | | 9 | | | S10350 | BLU | | | 115-199 |
| A-RD | | | | | 0-0 | 52-34-11 | SP00084 | | 9 | | | S10350 | RED | | | 001-099 |
| A-RD | | | AA | | 0-0 | 52-34-11 | SP00084 | | 9 | | | S10350 | RED | | | 115-199 |
| B-WT | | | | | 0-0 | 30-71-21 | B00117 | = 2 | | | | SP00279 | | 9 | | 001-099 |
| C-BK | | | | | 0-0 | 30-71-21 | SP00279 | | 9 | | | B00107 | = 1 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4104 | 286N4104 | | | | RIGHT MIX BAY AND FORWARD CARGO LIGHTS (continued) | | | | | | | | | | | | |
| C-BL | | | | | 0-0 | 52-34-11 | SP00094 | | | 9 | S10352 | BLU | | | 001-099 | | |
| C-BL | | | | AC | 0-0 | 52-34-11 | SP00094 | | | 9 | S10352 | BLU | | | 115-199 | | |
| C-RD | | | | | 0-0 | 52-34-11 | SP00092 | | | 9 | S10352 | RED | | | 001-099 | | |
| C-RD | | | | AC | 0-0 | 52-34-11 | SP00092 | | | 9 | S10352 | RED | | | 115-199 | | |
| D-WT | | | | | 0-0 | 30-71-21 | B00107 | = 2 | | | GD02382 | AC.. | E | | 001-099 | | |
| E-BL | | | | | 0-0 | 52-71-21 | SP00172 | | | 9 | S10083 | BLU | | | 001-099 | | |
| E-BL | | | | AE | 0-0 | 52-71-21 | SP00172 | | | 9 | S10083 | BLU | | | 115-199 | | |
| E-PR | | | | | 0-0 | 30-71-21 | SP00277 | | | 9 | B00085 | = 1 | | | 001-099 | | |
| E-RD | | | | | 0-0 | 52-71-21 | SP00170 | | | 9 | S10083 | RED | | | 001-099 | | |
| E-RD | | | | AE | 0-0 | 52-71-21 | SP00170 | | | 9 | S10083 | RED | | | 115-199 | | |
| F-GD | | | | | 0-0 | 30-71-21 | B00085 | = 2 | | | SP00426 | | 9 | | 001-099 | | |
| G-PR | | | | | 0-0 | 30-71-21 | SP00277 | | | 9 | B00043 | = 1 | | | 001-099 | | |
| H-GD | | | | | 0-0 | 30-71-21 | B00043 | = 2 | | | GD02380 | AC.. | E | | 001-099 | | |
| I-BK | | | | | 0-0 | 30-71-21 | B10102 | = 1 | | | SP00283 | | 9 | | 001-099 | | |
| I-GD | | | | | 0-0 | 30-71-21 | B10122 | = 2 | | | GD03001 | AC.. | E | | 001-099 | | |
| I-PR | | | | | 0-0 | 30-71-21 | SP00285 | | | 9 | B10122 | = 1 | | | 001-099 | | |
| J-WT | | | | | 0-0 | 30-71-21 | B10102 | = 2 | | | GD03001 | AC.. | E | | 001-099 | | |
| K-PR | | | | | 0-0 | 30-71-21 | B10104 | = 1 | | | SP00285 | | 9 | | 001-099 | | |
| L-GD | | | | | 0-0 | 30-71-21 | B10104 | = 2 | | | SP00283 | | 9 | | 001-099 | | |
| T-BK | | | | | 0-0 | 30-71-21 | B00118 | = 1 | | | SP00323 | | 9 | | 002-099 | | |
| T-WT | | | | | 0-0 | 30-71-21 | B00118 | = 2 | | | GD02378 | AC.. | E | | 002-099 | | |
| W4106 | 286N4106 | | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM | | | | | | | | | | | | |
| 0001 | 24 | | GK | | 25-0 | 21-51-22 | D40666P | | | 1 | D40064P | | 8 | | 001-099 | | |
| 0002 | 24 | | GK | | 25-0 | 21-51-22 | D40666P | | | 2 | D40064P | | 56 | | 001-099 | | |
| 0003 | 24 | | GK | | 25-0 | 21-51-22 | D40666P | | | 3 | D40064P | | 51 | | 001-099 | | |
| 0004 | 24 | | GK | | 25-0 | 21-51-22 | D40666P | | | 4 | D40064P | | 39 | | 001-099 | | |
| 0005 | 24 | | GK | | 25-0 | 21-51-22 | D40666P | | | 5 | D40064P | | 23 | | 001-099 | | |
| 0006 | 24 | | GK | | 25-0 | 21-51-22 | D40666P | | | 6 | D40064P | | 22 | | 001-099 | | |
| 0007 | 24 | | GK | | 25-0 | 21-51-22 | D40666P | | | 7 | D40064P | | 9 | | 001-099 | | |
| 0031 | 20 | | GA | | 50-0 | 36-11-22 | D40064P | | | 12 | D41210J | | 4 | | 001-099 | | |
| 0031 | 20 | | GA | | 49-0 | 36-11-22 | D40064P | | | 12 | D41210J | | 4 | | 115-199 | | |
| 0032 | 20 | | GA | | 50-0 | 36-11-22 | D40064P | | | 46 | D41210J | | 5 | | 001-099 | | |
| 0032 | 20 | | GA | | 49-0 | 36-11-22 | D40064P | | | 46 | D41210J | | 5 | | 115-199 | | |
| 0034 | 24 | | GK | | 50-0 | 36-11-22 | D40064P | | | 7 | D41210J | | 7 | | 001-099 | | |
| 0034 | 24 | | GK | | 49-0 | 36-11-22 | D40064P | | | 7 | D41210J | | 7 | | 115-199 | | |
| 0035 | 24 | | GK | | 34-0 | 21-61-11 | D02550 | | | 1 | D40064P | | 11 | | ALL | | |
| 0036 | 20 | | GA | | 3-0 | 21-61-11 | D02550 | | | 2 | GD00921 | DC.. | E | | ALL | | |
| 0037 | 24 | | GK | | 30-0 | 21-61-31 | D41640J | | | 4 | D40064P | | 13 | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | |
| 0037 | 24 | | GK | | 46-0 | 21-61-31 | D41640J | | 1 | | D40064P | | 13 | | 115-199 |
| 0039 | 24 | | GK | | 30-0 | 21-61-21 | D41640J | | 1 | | D40064P | | 14 | | 001-099 |
| 0039 | 24 | | GK | | 46-0 | 21-61-21 | D41640J | | 2 | | D40064P | | 14 | | 115-199 |
| 0041 | 20 | | GA | | 55-0 | 21-51-21 | D40068J | | 1 | | D40976P | | 1 | | ALL |
| 0042 | 20 | | GA | | 55-0 | 21-51-21 | D40068J | | 19 | | D40976P | | 2 | | ALL |
| 0043 | 20 | | GA | | 55-0 | 21-51-21 | D40068J | | 20 | | D40976P | | 3 | | ALL |
| 0044 | 20 | | GA | | 55-0 | 21-51-21 | D40068J | | 21 | | D40976P | | 23 | | ALL |
| 0047 | 24 | | GK | | 8-0 | 21-51-23 | D40976P | | 9 | | D41546P | | 37 | | 001-099 |
| 0047 | 24 | | GK | | 50-0 | 21-51-23 | D40976P | | 9 | | D41642J | | 1 | | 115-199 |
| 0048 | 24 | | GK | | 8-0 | 21-51-23 | D40976P | | 20 | | D41546P | | 38 | | 001-099 |
| 0048 | 24 | | GK | | 50-0 | 21-51-23 | D40976P | | 20 | | D41642J | | 2 | | 115-199 |
| 0049 | 24 | | GK | | 8-0 | 21-51-23 | D40976P | | 8 | | D41546P | | 48 | | 001-099 |
| 0049 | 24 | | GK | | 50-0 | 21-51-23 | D40976P | | 8 | | D41642J | | 3 | | 115-199 |
| 0050 | 24 | | GK | | 8-0 | 21-51-23 | D40976P | | 10 | | D40064P | | 17 | | 001-099 |
| 0050 | 24 | | GK | | 50-0 | 21-51-23 | D40976P | | 10 | | D41642J | | 4 | | 115-199 |
| 0051 | 24 | | GK | | 8-0 | 21-51-23 | D40976P | | 11 | | D40064P | | 25 | | 001-099 |
| 0051 | 24 | | GK | | 50-0 | 21-51-23 | D40976P | | 11 | | D41642J | | 5 | | 115-199 |
| 0052 | 24 | | GK | | 8-0 | 21-51-23 | D40976P | | 12 | | D40064P | | 26 | | 001-099 |
| 0052 | 24 | | GK | | 50-0 | 21-51-23 | D40976P | | 12 | | D41642J | | 6 | | 115-199 |
| 0054 | 24 | | GK | | 54-0 | 21-51-23 | D40976P | | 14 | | D41102J | | 22 | | 001-099 |
| 0054 | 24 | | GK | | 55-0 | 21-51-23 | D40976P | | 14 | | D41102J | | 22 | | 115-199 |
| 0055 | 24 | | GK | | 54-0 | 21-51-23 | D40976P | | 15 | | D41102J | | 23 | | 001-099 |
| 0055 | 24 | | GK | | 55-0 | 21-51-23 | D40976P | | 15 | | D41102J | | 23 | | 115-199 |
| 0056 | 24 | | GK | | 54-0 | 21-51-23 | D40976P | | 16 | | D41102J | | 25 | | 001-099 |
| 0056 | 24 | | GK | | 55-0 | 21-51-23 | D40976P | | 16 | | D41102J | | 25 | | 115-199 |
| 0057 | 24 | | GK | | 54-0 | 21-51-23 | D40976P | | 17 | | D41102J | | 28 | | 001-099 |
| 0057 | 24 | | GK | | 55-0 | 21-51-23 | D40976P | | 17 | | D41102J | | 28 | | 115-199 |
| 0058 | 24 | | GK | | 54-0 | 21-51-23 | D40976P | | 18 | | D41102J | | 26 | | 001-099 |
| 0058 | 24 | | GK | | 55-0 | 21-51-23 | D40976P | | 18 | | D41102J | | 26 | | 115-199 |
| 0059 | 24 | | GK | | 54-0 | 21-51-23 | D40976P | | 19 | | D41102J | | 27 | | 001-099 |
| 0059 | 24 | | GK | | 55-0 | 21-51-23 | D40976P | | 19 | | D41102J | | 27 | | 115-199 |
| 0060 | 20 | | GA | | 50-0 | 21-51-23 | D41546P | | 41 | | D41102J | | 1 | | 001-099 |
| 0060 | 20 | | GA | | 13-0 | 21-51-23 | D41638J | | 1 | | D41102J | | 1 | | 115-199 |
| 0061 | 20 | | GA | | 50-0 | 21-51-23 | D41546P | | 45 | | D41102J | | 2 | | 001-099 |
| 0061 | 20 | | GA | | 13-0 | 21-51-23 | D41638J | | 2 | | D41102J | | 2 | | 115-199 |
| 0062 | 20 | | GA | | 50-0 | 21-51-23 | D41546P | | 35 | | D41102J | | 3 | | 001-099 |
| 0062 | 20 | | GA | | 13-0 | 21-51-23 | D41638J | | 3 | | D41102J | | 3 | | 115-199 |
| 0063 | 20 | | GA | | 50-0 | 21-51-23 | D41546P | | 36 | | D41102J | | 4 | | 001-099 |
| 0063 | 20 | | GA | | 13-0 | 21-51-23 | D41638J | | 4 | | D41102J | | 4 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | |
| 0064 | 20 | | GA | | 50-0 | 21-51-23 | D40064P | 29 | | | D41102J | 5 | | | 001-099 |
| 0064 | 20 | | GA | | 13-0 | 21-51-23 | D41638J | 5 | | | D41102J | 5 | | | 115-199 |
| 0065 | 20 | | GA | | 50-0 | 21-51-23 | D40064P | 28 | | | D41102J | 6 | | | 001-099 |
| 0065 | 20 | | GA | | 13-0 | 21-51-23 | D41638J | 6 | | | D41102J | 6 | | | 115-199 |
| 0066 | 24 | | GK | | 27-0 | 21-51-24 | D40064P | 36 | | | D40670P | 1 | | | 001-099 |
| 0067 | 24 | | GK | | 8-0 | 21-51-24 | D40064P | 45 | | | D40976P | 4 | | | 001-099 |
| 0067 | 24 | | GK | | 50-0 | 21-51-24 | D41642J | 7 | | | D40976P | 4 | | | 115-199 |
| 0077 | 24 | | GK | | 26-0 | 30-71-21 | D40064P | 44 | | | SP00422 | | 9 | | 115-199 |
| 0083 | 24 | | GK | | 51-0 | 36-21-11 | D40064P | 30 | | | D40068J | 45 | | | 001-099 |
| 0083 | 24 | | GK | | 50-0 | 36-21-11 | D40064P | 30 | | | D40068J | 45 | | | 115-199 |
| 0084 | 20 | | GA | | 50-0 | 36-11-21 | D40064P | 33 | | | D41210J | 1 | | | 001-099 |
| 0084 | 20 | | GA | | 49-0 | 36-11-21 | D40064P | 33 | | | D41210J | 1 | | | 115-199 |
| 0085 | 20 | | GA | | 50-0 | 36-11-21 | D40064P | 34 | | | D41210J | 2 | | | 001-099 |
| 0085 | 20 | | GA | | 49-0 | 36-11-21 | D40064P | 34 | | | D41210J | 2 | | | 115-199 |
| 0086 | 20 | | GA | | 50-0 | 36-11-21 | D40064P | 35 | | | D41210J | 3 | | | 001-099 |
| 0086 | 20 | | GA | | 49-0 | 36-11-21 | D40064P | 35 | | | D41210J | 3 | | | 115-199 |
| 0089 | 20 | | GA | | 50-0 | 30-71-11 | D40070J | 22 | | | D40064P | 38 | | | ALL |
| 0090 | 20 | | GA | | 50-0 | 33-44-11 | D40064P | 6 | | | D41102J | 9 | | | ALL |
| 0091 | 24 | | GK | | 80-0 | 30-71-21 | SP00422 | | 9 | | SP00420 | | 9 | | 115-199 |
| 0093 | 20 | | GA | | 46-0 | 28-25-11 | D41546P | 51 | | | D41640J | 3 | | | 115-199 |
| 0094 | 24 | | GK | | 46-0 | 36-22-11 | D40064P | 40 | | | SM00004 | | 9 | | 001-099 |
| 0094 | 24 | | GK | | 46-0 | 36-22-11 | SM00004 | | 9 | | D40064P | 40 | | | 115-199 |
| 0095 | 24 | | GK | | 41-0 | 36-22-11 | D42086P | 28 | | | SM00004 | | 9 | | 001-099 |
| 0095 | 24 | | GK | | 41-0 | 36-22-11 | SM00004 | | 9 | | D42086P | 28 | | | 115-199 |
| 0104 | 24 | | GK | | 46-0 | 21-51-22 | D40064P | 57 | | | D41640J | 4 | | | 115-199 |
| 0105 | 24 | | GK | | 8-0 | SPARE | D40064P | 58 | | | D40976P | 24 | | | 001-099 |
| 0105 | 24 | | GK | | 9-0 | 21-51-11 | D40064P | 58 | | | D40976P | 24 | | | 115-199 |
| 0107 | 24 | | GK | | 8-0 | 21-51-21 | D40064P | 60 | | | D40976P | 26 | | | 001-099 |
| 0107 | 24 | | GK | | 9-0 | 21-51-21 | D40064P | 60 | | | D40976P | 26 | | | 115-199 |
| 0108 | 24 | | GK | | 8-0 | 21-51-21 | D40064P | 61 | | | D40976P | 27 | | | 001-099 |
| 0108 | 24 | | GK | | 9-0 | 21-51-21 | D40064P | 61 | | | D40976P | 27 | | | 115-199 |
| 0109 | 24 | | GK | | 9-0 | SPARE | D40976P | 21 | | | D40064P | 47 | | | 115-199 |
| 0110 | 24 | | GK | | 51-0 | 36-11-22 | D40064P | 48 | | | D40068J | 4 | | | 001-099 |
| 0110 | 24 | | GK | | 50-0 | 36-11-22 | D40064P | 48 | | | D40068J | 4 | | | 115-199 |
| 0111 | 24 | | GK | | 6-0 | 36-22-11 | SM00004 | | 9 | | D40068J | 51 | | | 001-099 |
| 0111 | 24 | | GK | | 5-0 | 36-22-11 | SM00004 | | 9 | | D40068J | 5 | | | 115-199 |
| 0121 | 24 | | GK | | 2-0 | 21-65-12 | D04648 | | B | | SM00013 | | 9 | | ALL |
| 0122 | 22 | | GA | | 8-0 | 36-11-22 | D40068J | 9 | | | D41210J | 13 | | | 001-099 |
| 0122 | 22 | | GA | | 8-0 | 36-11-22 | D41210J | 13 | | | D40068J | 9 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | To | | | | | | | | | |
|------------|-------------|----|-------|---|------|----------|---------|---------|-------|------|---------|--------|-------|------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | |
| 0139 | 20 | GA | | | 3-0 | 21-65-12 | GD00921 | DC.. | E | | SM00013 | | 9 | | ALL |
| 0150 | 24 | GK | | | 13-0 | SPARE | D41638J | 48 | | | D40068J | 22 | | | 115-199 |
| 0151 | 24 | GK | | | 13-0 | SPARE | D41638J | 49 | | | D40068J | 32 | | | 115-199 |
| 0157 | 24 | GK | | | 46-0 | SPARE | D41546P | 49 | | | D41640J | 53 | | | 115-199 |
| 0162 | 24 | GK | | | 46-0 | SPARE | D41642J | 41 | | | D40064P | 24 | | | 115-199 |
| 0163 | 22 | GA | | | 11-0 | 29-32-21 | D42086P | 29 | | | SP00099 | | 9 | | 001-099 |
| 0163 | 22 | GA | | | 7-0 | 29-32-21 | D42086P | 29 | | | SP00099 | | 9 | | 115-199 |
| 0166 | 24 | GK | | | 8-0 | 21-51-23 | D40976P | 13 | | | D40064P | 27 | | | 001-099 |
| 0166 | 24 | GK | | | 50-0 | 21-51-23 | D40976P | 13 | | | D41642J | 8 | | | 115-199 |
| 0167 | 24 | GK | | | 8-0 | 21-51-25 | D40064P | 18 | | | D40976P | 7 | | | 001-099 |
| 0167 | 24 | GK | | | 50-0 | 21-51-25 | D41642J | 9 | | | D40976P | 7 | | | 115-199 |
| 0168 | 24 | GK | | | 25-0 | 21-51-25 | D40064P | 19 | | | D40666P | 8 | | | 001-099 |
| 0169 | 24 | GK | | | 8-0 | 21-51-25 | D40064P | 20 | | | D40976P | 41 | | | 001-099 |
| 0169 | 24 | GK | | | 50-0 | 21-51-25 | D41642J | 10 | | | D40976P | 41 | | | 115-199 |
| 0170 | 24 | GK | | | 24-0 | 21-51-25 | D40666P | 35 | | | D42086P | 31 | | | 001-099 |
| 0170 | 24 | GK | | | 42-0 | 21-51-25 | D41642J | 11 | | | D42086P | 31 | | | 115-199 |
| 0171 | 24 | GK | | | 25-0 | 21-51-25 | D40064P | 21 | | | D40666P | 36 | | | 001-099 |
| 0172 | 24 | GK | | | 54-0 | 21-51-25 | D40976P | 38 | | | D41102J | 10 | | | 001-099 |
| 0172 | 24 | GK | | | 55-0 | 21-51-25 | D40976P | 38 | | | D41102J | 10 | | | 115-199 |
| 0173 | 24 | GK | | | 54-0 | 21-51-25 | D40976P | 39 | | | D41102J | 11 | | | 001-099 |
| 0173 | 24 | GK | | | 55-0 | 21-51-25 | D40976P | 39 | | | D41102J | 11 | | | 115-199 |
| 0174 | 24 | GK | | | 27-0 | 21-61-11 | D40670P | 11 | | | D41546P | 5 | | | 001-099 |
| 0174 | 24 | GK | | | 46-0 | 21-61-11 | D41640J | 5 | | | D41546P | 5 | | | 115-199 |
| 0175 | 24 | GK | | | 27-0 | 21-61-11 | D40670P | 12 | | | D41546P | 4 | | | 001-099 |
| 0175 | 24 | GK | | | 46-0 | 21-61-11 | D41640J | 6 | | | D41546P | 4 | | | 115-199 |
| 0176 | 24 | GK | | | 27-0 | 21-61-11 | D40670P | 13 | | | D41546P | 3 | | | 001-099 |
| 0176 | 24 | GK | | | 46-0 | 21-61-11 | D41640J | 7 | | | D41546P | 3 | | | 115-199 |
| 0177 | 24 | GK | | | 27-0 | 21-61-11 | D40670P | 14 | | | D41546P | 2 | | | 001-099 |
| 0177 | 24 | GK | | | 46-0 | 21-61-11 | D41640J | 8 | | | D41546P | 2 | | | 115-199 |
| 0178 | 24 | GK | | | 27-0 | 21-61-11 | D40670P | 15 | | | D41546P | 1 | | | 001-099 |
| 0178 | 24 | GK | | | 46-0 | 21-61-11 | D41640J | 9 | | | D41546P | 1 | | | 115-199 |
| 0179 | 24 | GK | | | 59-0 | 21-61-11 | D41546P | 9 | | | D02546 | 10 | | | 001-099 |
| 0179 | 24 | GK | | | 58-0 | 21-61-11 | D41546P | 9 | | | D02546 | 10 | | | 115-199 |
| 0180 | 24 | GK | | | 59-0 | 21-61-11 | D41546P | 10 | | | D02546 | 1 | | | 001-099 |
| 0180 | 24 | GK | | | 58-0 | 21-61-11 | D41546P | 10 | | | D02546 | 1 | | | 115-199 |
| 0181 | 20 | GA | | | 4-0 | 21-61-11 | D02546 | 3 | | | GD00880 | AC.. | E | | ALL |
| 0182 | 20 | GA | | | 4-0 | 21-61-11 | D02546 | 13 | | | GD00884 | ST.. | E | | ALL |
| 0183 | 24 | GK | | | 59-0 | 21-61-11 | D02546 | 11 | | | D41546P | 50 | | | 001-099 |
| 0183 | 24 | GK | | | 58-0 | 21-61-11 | D02546 | 11 | | | D41546P | 50 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4106 | 286N4106 | | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | | |
| 0184 | 24 | | GK | | 59-0 | 21-61-21 | D41546P | | | 52 | | D02560 | | 2 | | 001-099 | |
| 0184 | 24 | | GK | | 58-0 | 21-61-21 | D41546P | | | 52 | | D02560 | | 2 | | 115-199 | |
| 0185 | 24 | | GK | | 58-0 | 21-61-31 | D41546P | | | 54 | | D02574 | | 2 | | ALL | |
| 0186 | 24 | | GK | | 59-0 | 21-61-21 | D41546P | | | 11 | | D02560 | | 10 | | 001-099 | |
| 0186 | 24 | | GK | | 58-0 | 21-61-21 | D41546P | | | 11 | | D02560 | | 10 | | 115-199 | |
| 0187 | 24 | | GK | | 59-0 | 21-61-21 | D41546P | | | 12 | | D02560 | | 1 | | 001-099 | |
| 0187 | 24 | | GK | | 58-0 | 21-61-21 | D41546P | | | 12 | | D02560 | | 1 | | 115-199 | |
| 0188 | 20 | | GA | | 3-0 | 21-61-21 | D02560 | | | 3 | | GD00880 | AC.. | E | | ALL | |
| 0189 | 20 | | GA | | 3-0 | 21-61-21 | D02560 | | | 13 | | GD00884 | ST.. | E | | ALL | |
| 0190 | 24 | | GK | | 59-0 | 21-61-11 | D02546 | | | 2 | | D41546P | | 46 | | 001-099 | |
| 0190 | 24 | | GK | | 58-0 | 21-61-11 | D02546 | | | 2 | | D41546P | | 46 | | 115-199 | |
| 0191 | 24 | | GK | | 59-0 | 21-61-21 | D41546P | | | 53 | | D02560 | | 11 | | 001-099 | |
| 0191 | 24 | | GK | | 58-0 | 21-61-21 | D41546P | | | 53 | | D02560 | | 11 | | 115-199 | |
| 0192 | 24 | | GK | | 58-0 | 21-61-31 | D02574 | | | 11 | | D41546P | | 55 | | ALL | |
| 0193 | 24 | | GK | | 27-0 | 21-61-21 | D40670P | | | 26 | | D41546P | | 17 | | 001-099 | |
| 0193 | 24 | | GK | | 46-0 | 21-61-21 | D41640J | | | 10 | | D41546P | | 17 | | 115-199 | |
| 0194 | 24 | | GK | | 27-0 | 21-61-21 | D40670P | | | 27 | | D41546P | | 16 | | 001-099 | |
| 0194 | 24 | | GK | | 46-0 | 21-61-21 | D41640J | | | 11 | | D41546P | | 16 | | 115-199 | |
| 0195 | 24 | | GK | | 27-0 | 21-61-21 | D40670P | | | 28 | | D41546P | | 15 | | 001-099 | |
| 0195 | 24 | | GK | | 46-0 | 21-61-21 | D41640J | | | 12 | | D41546P | | 15 | | 115-199 | |
| 0196 | 24 | | GK | | 27-0 | 21-61-21 | D40670P | | | 29 | | D41546P | | 14 | | 001-099 | |
| 0196 | 24 | | GK | | 46-0 | 21-61-21 | D41640J | | | 13 | | D41546P | | 14 | | 115-199 | |
| 0197 | 24 | | GK | | 27-0 | 21-61-21 | D40670P | | | 30 | | D41546P | | 13 | | 001-099 | |
| 0197 | 24 | | GK | | 46-0 | 21-61-21 | D41640J | | | 14 | | D41546P | | 13 | | 115-199 | |
| 0201 | 24 | | GK | | 27-0 | 21-61-31 | D40844P | | | 9 | | D41546P | | 27 | | 001-099 | |
| 0201 | 24 | | GK | | 46-0 | 21-61-31 | D41640J | | | 15 | | D41546P | | 27 | | 115-199 | |
| 0202 | 24 | | GK | | 27-0 | 21-61-31 | D40844P | | | 6 | | D41546P | | 28 | | 001-099 | |
| 0202 | 24 | | GK | | 46-0 | 21-61-31 | D41640J | | | 16 | | D41546P | | 28 | | 115-199 | |
| 0203 | 24 | | GK | | 27-0 | 21-61-31 | D40844P | | | 7 | | D41546P | | 29 | | 001-099 | |
| 0203 | 24 | | GK | | 46-0 | 21-61-31 | D41640J | | | 17 | | D41546P | | 29 | | 115-199 | |
| 0204 | 24 | | GK | | 27-0 | 21-61-31 | D40844P | | | 8 | | D41546P | | 30 | | 001-099 | |
| 0204 | 24 | | GK | | 46-0 | 21-61-31 | D41640J | | | 18 | | D41546P | | 30 | | 115-199 | |
| 0210 | 24 | | GK | | 27-0 | 21-61-31 | D40844P | | | 5 | | D41546P | | 26 | | 001-099 | |
| 0210 | 24 | | GK | | 46-0 | 21-61-31 | D41640J | | | 19 | | D41546P | | 26 | | 115-199 | |
| 0211 | 24 | | GK | | 58-0 | 21-61-31 | D41546P | | | 24 | | D02574 | | 10 | | ALL | |
| 0212 | 24 | | GK | | 58-0 | 21-61-31 | D41546P | | | 25 | | D02574 | | 1 | | ALL | |
| 0213 | 20 | | GA | | 3-0 | 21-61-31 | D02574 | | | 3 | | GD00880 | AC.. | E | | ALL | |
| 0214 | 20 | | GA | | 3-0 | 21-61-31 | D02574 | | | 13 | | GD00884 | ST.. | E | | ALL | |
| 0218 | 22 | | GA | | 53-0 | 32-42-12 | D41642J | | | 12 | | D41810P | | 1 | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | | To | | | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | | |
| 0219 | 22 | GA | | | 53-0 | 32-42-12 | D41642J | | 13 | | | D41810P | 2 | | | 115-199 |
| 0220 | 22 | GA | | | 53-0 | 32-42-12 | D41642J | | 14 | | | D41810P | 3 | | | 115-199 |
| 0221 | 22 | GA | | | 53-0 | 32-42-12 | D41642J | | 15 | | | D41810P | 4 | | | 115-199 |
| 0222 | 22 | GA | | | 53-0 | 32-42-12 | D41642J | | 16 | | | D41810P | 5 | | | 115-199 |
| 0223 | 22 | GA | | | 53-0 | 32-42-12 | D41642J | | 17 | | | D41810P | 6 | | | 115-199 |
| 0224 | 22 | GA | | | 53-0 | 32-42-12 | D41642J | | 18 | | | D41810P | 7 | | | 115-199 |
| 0225 | 22 | GA | | | 46-0 | 52-35-11 | D41546P | | 41 | | | D41640J | 20 | | | 115-199 |
| 0226 | 22 | GA | | | 46-0 | 52-35-11 | D41546P | | 35 | | | D41640J | 21 | | | 115-199 |
| 0227 | 22 | GA | | | 46-0 | 52-35-11 | D41546P | | 36 | | | D41640J | 22 | | | 115-199 |
| 0232 | 20 | GA | | | 46-0 | 28-25-11 | D41546P | | 38 | | | D41640J | 23 | | | 115-199 |
| 0233 | 22 | GA | | | 46-0 | 32-42-12 | D41640J | | 24 | | | D41546P | 48 | | | 115-199 |
| 0234 | 22 | GA | | | 46-0 | 32-42-12 | D41640J | | 25 | | | D41546P | 37 | | | 115-199 |
| 0240 | 24 | GK | | | 8-0 | 21-51-23 | D40976P | | 40 | | | D41546P | 47 | | | 001-099 |
| 0240 | 24 | GK | | | 10-0 | 21-51-23 | D40976P | | 40 | | | D41546P | 47 | | | 115-199 |
| 0241 | 20 | GA | | | 25-0 | 21-51-22 | D40666P | | 48 | | | D40064P | 3 | | | 001-099 |
| 0241 | 20 | GA | | | 46-0 | 21-51-22 | D41640J | | 26 | | | D40064P | 3 | | | 115-199 |
| 0242 | 24 | GK | | | 25-0 | SPARE | D40666P | | 39 | | | D40064P | 55 | | | 001-099 |
| 0242 | 24 | GK | | | 46-0 | SPARE | D41640J | | 27 | | | D40064P | 55 | | | 115-199 |
| 0243 | 24 | GK | | | 25-0 | SPARE | D40666P | | 40 | | | D40064P | 54 | | | 001-099 |
| 0243 | 24 | GK | | | 46-0 | SPARE | D41640J | | 28 | | | D40064P | 54 | | | 115-199 |
| 0244 | 22 | GA | | | 25-0 | SPARE | D40666P | | 41 | | | D40064P | 52 | | | 001-099 |
| 0244 | 22 | GA | | | 46-0 | SPARE | D41642J | | 42 | | | D40064P | 52 | | | 115-199 |
| 0245 | 22 | GA | | | 25-0 | SPARE | D40666P | | 42 | | | D40064P | 53 | | | 001-099 |
| 0245 | 22 | GA | | | 46-0 | SPARE | D41642J | | 43 | | | D40064P | 53 | | | 115-199 |
| 0248 | 24 | GK | | | 24-0 | SPARE | D40666P | | 49 | | | D42086P | 34 | | | 001-099 |
| 0248 | 24 | GK | | | 42-0 | SPARE | D41642J | | 34 | | | D42086P | 34 | | | 115-199 |
| 0249 | 24 | GK | | | 24-0 | SPARE | D40666P | | 50 | | | D42086P | 35 | | | 001-099 |
| 0249 | 24 | GK | | | 42-0 | SPARE | D41642J | | 35 | | | D42086P | 35 | | | 115-199 |
| 0252 | 24 | GK | | | 6-0 | 21-52-11 | SM00001 | | 9 | | | D40068J | 55 | | | 001-099 |
| 0252 | 24 | GK | | | 5-0 | 21-52-11 | SM00001 | | 9 | | | D40068J | 55 | | | 115-199 |
| 0253 | 24 | GK | | | 0-20 | 21-52-11 | SM00001 | | 9 | | | GD02539 | DC.. | E | | 001-099 |
| 0253 | 24 | GK | | | 0-12 | 21-52-11 | SM00001 | | 9 | | | GD02539 | DC.. | E | | 115-199 |
| 0254 | 24 | GK | | | 6-0 | 21-52-11 | SM00001 | | 9 | | | D40068J | 12 | | | 001-099 |
| 0255 | 24 | GK | | | 6-0 | 21-52-11 | SM00002 | | 9 | | | D40068J | 14 | | | 001-099 |
| 0256 | 24 | GK | | | 0-12 | 21-52-11 | SM00002 | | 9 | | | GD02539 | DC.. | E | | 001-099 |
| 0257 | 24 | GK | | | 6-0 | 21-52-11 | SM00002 | | 9 | | | D40068J | 16 | | | 001-099 |
| 0258 | 24 | GK | | | 6-0 | 21-52-11 | SM00003 | | 9 | | | D40068J | 18 | | | 001-099 |
| 0259 | 24 | GK | | | 0-12 | 21-52-11 | SM00003 | | 9 | | | GD02539 | DC.. | E | | 001-099 |
| 0260 | 24 | GK | | | 6-0 | 21-52-11 | SM00003 | | 9 | | | D40068J | 10 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | |
| 2000B | 24 | GL | AD | | 13-0 | SPARE | D41638J | 37 | | | D40070J | 25 | | | 115-199 |
| 2000R | 24 | GL | AD | | 0-0 | SPARE | D41638J | 38 | | | D40070J | 24 | | | 115-199 |
| 2001B | 24 | GL | DP | | 33-0 | 21-61-21 | D41640J | 3 | | | D40670P | 35 | | | 001-099 |
| 2001R | 24 | GL | DP | | 0-0 | 21-61-21 | D41640J | 2 | | | D40670P | 34 | | | 001-099 |
| 2002B | 24 | GL | AB | | 51-0 | 36-21-11 | D40064P | 32 | | | D40068J | 47 | | | 001-099 |
| 2002B | 24 | GL | AB | | 50-0 | 36-21-11 | D40064P | 32 | | | D40068J | 47 | | | 115-199 |
| 2002R | 24 | GL | AB | | 0-0 | 36-21-11 | D40064P | 31 | | | D40068J | 46 | | | ALL |
| 2003B | 24 | GL | AC | | 46-0 | 21-52-31 | D40070J | 5 | | | D42086P | 18 | | | 001-099 |
| 2003B | 24 | GL | AC | | 45-0 | 21-52-31 | D40070J | 5 | | | D42086P | 18 | | | 115-199 |
| 2003R | 24 | GL | AC | | 0-0 | 21-52-31 | D40070J | 6 | | | D42086P | 17 | | | ALL |
| 2009B | 24 | GL | AJ | | 46-0 | 21-52-31 | D42086P | 23 | | | D40070J | 7 | | | 001-099 |
| 2009B | 24 | GL | AJ | | 45-0 | 21-52-31 | D42086P | 23 | | | D40070J | 7 | | | 115-199 |
| 2009R | 24 | GL | AJ | | 0-0 | 21-52-31 | D42086P | 22 | | | D40070J | 8 | | | ALL |
| 2011B | 24 | GL | AL | | 25-0 | 21-65-12 | D42086P | 52 | | | D41640J | 17 | | | 001-099 |
| 2011B | 24 | GL | AL | | 42-0 | 21-65-12 | D42086P | 52 | | | D41642J | 19 | | | 115-199 |
| 2011R | 24 | GL | AL | | 0-0 | 21-65-12 | D42086P | 53 | | | D41640J | 19 | | | 001-099 |
| 2011R | 24 | GL | AL | | 0-0 | 21-65-12 | D42086P | 53 | | | D41642J | 20 | | | 115-199 |
| 2014B | 24 | GL | AS | | 46-0 | 21-52-11 | D42086P | 1 | | | D40068J | 54 | | | 001-099 |
| 2014B | 24 | GL | AS | | 45-0 | 21-52-11 | D42086P | 1 | | | D40068J | 54 | | | 115-199 |
| 2014R | 24 | GL | AS | | 0-0 | 21-52-11 | D42086P | 2 | | | SM00001 | | 9 | | ALL |
| 2015B | 24 | GL | AO | | 46-0 | 21-52-11 | D42086P | 3 | | | D40068J | 11 | | | 001-099 |
| 2015R | 24 | GL | AO | | 0-0 | 21-52-11 | D42086P | 4 | | | SM00001 | | 9 | | 001-099 |
| 2016B | 24 | GL | AP | | 46-0 | 21-52-11 | D42086P | 5 | | | D40068J | 13 | | | 001-099 |
| 2016R | 24 | GL | AP | | 0-0 | 21-52-11 | D42086P | 6 | | | SM00002 | | 9 | | 001-099 |
| 2017B | 24 | GL | AQ | | 46-0 | 21-52-11 | D42086P | 7 | | | D40068J | 15 | | | 001-099 |
| 2017R | 24 | GL | AQ | | 0-0 | 21-52-11 | D42086P | 8 | | | SM00002 | | 9 | | 001-099 |
| 2018B | 24 | GL | AR | | 46-0 | 21-52-11 | D42086P | 9 | | | D40068J | 17 | | | 001-099 |
| 2018R | 24 | GL | AR | | 0-0 | 21-52-11 | D42086P | 10 | | | SM00003 | | 9 | | 001-099 |
| 2019B | 24 | GL | AT | | 25-0 | 21-65-12 | D42086P | 50 | | | D41640J | 13 | | | 001-099 |
| 2019B | 24 | GL | AT | | 42-0 | 21-65-12 | D42086P | 50 | | | D41642J | 21 | | | 115-199 |
| 2019R | 24 | GL | AT | | 0-0 | 21-65-12 | D42086P | 51 | | | D41640J | 15 | | | 001-099 |
| 2019R | 24 | GL | AT | | 0-0 | 21-65-12 | D42086P | 51 | | | D41642J | 22 | | | 115-199 |
| 2020B | 24 | GL | AU | | 50-0 | 21-51-22 | D40064P | 24 | | | D40070J | 4 | | | 001-099 |
| 2020B | 24 | GL | AU | | 13-0 | 21-51-22 | D41638J | 7 | | | D40070J | 4 | | | 115-199 |
| 2020R | 24 | GL | AU | | 0-0 | 21-51-22 | D40064P | 47 | | | D40070J | 3 | | | 001-099 |
| 2020R | 24 | GL | AU | | 0-0 | 21-51-22 | D41638J | 8 | | | D40070J | 3 | | | 115-199 |
| 2021B | 24 | GL | DJ | | 27-0 | 21-51-24 | D40064P | 37 | | | D40670P | 3 | | | 001-099 |
| 2021R | 24 | GL | DJ | | 0-0 | 21-51-24 | D40064P | 41 | | | D40670P | 2 | | | 001-099 |
| 2022B | 24 | GL | DK | | 25-0 | 21-51-24 | D40064P | 42 | | | D40666P | 11 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | | To | | | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | | |
| 2022R | 24 | GL | DK | | 0-0 | 21-51-24 | D40064P | | 43 | | | D40666P | | 12 | | 001-099 |
| 2023B | 24 | GL | BH | | 55-0 | 21-51-24 | D40670P | | 5 | | | D40068J | | 43 | | 001-099 |
| 2023B | 24 | GL | BH | | 13-0 | 21-51-24 | D41638J | | 9 | | | D40068J | | 43 | | 115-199 |
| 2023R | 24 | GL | BH | | 0-0 | 21-51-24 | D40670P | | 4 | | | D40068J | | 42 | | 001-099 |
| 2023R | 24 | GL | BH | | 0-0 | 21-51-24 | D41638J | | 10 | | | D40068J | | 42 | | 115-199 |
| 2024B | 24 | GL | BI | | 55-0 | 21-51-24 | D40670P | | 7 | | | D40068J | | 48 | | 001-099 |
| 2024B | 24 | GL | BI | | 13-0 | 21-51-24 | D41638J | | 11 | | | D40068J | | 48 | | 115-199 |
| 2024R | 24 | GL | BI | | 0-0 | 21-51-24 | D40670P | | 6 | | | D40068J | | 44 | | 001-099 |
| 2024R | 24 | GL | BI | | 0-0 | 21-51-24 | D41638J | | 12 | | | D40068J | | 44 | | 115-199 |
| 2025B | 24 | GL | BJ | | 51-0 | 21-51-24 | D40064P | | 50 | | | D40068J | | 50 | | 001-099 |
| 2025B | 24 | GL | BJ | | 13-0 | 21-51-24 | D41638J | | 13 | | | D40068J | | 50 | | 115-199 |
| 2025R | 24 | GL | BJ | | 0-0 | 21-51-24 | D40064P | | 49 | | | D40068J | | 49 | | 001-099 |
| 2025R | 24 | GL | BJ | | 0-0 | 21-51-24 | D41638J | | 14 | | | D40068J | | 49 | | 115-199 |
| 2026B | 24 | GL | BK | | 53-0 | 21-51-25 | D40666P | | 37 | | | D41102J | | 12 | | 001-099 |
| 2026B | 24 | GL | BK | | 13-0 | 21-51-25 | D41638J | | 15 | | | D41102J | | 12 | | 115-199 |
| 2026R | 24 | GL | BK | | 0-0 | 21-51-25 | D40666P | | 38 | | | D41102J | | 13 | | 001-099 |
| 2026R | 24 | GL | BK | | 0-0 | 21-51-25 | D41638J | | 16 | | | D41102J | | 13 | | 115-199 |
| 2027B | 24 | GL | BL | | 27-0 | 21-61-11 | D40670P | | 22 | | | D41546P | | 31 | | 001-099 |
| 2027B | 24 | GL | BL | | 46-0 | 21-61-11 | D41640J | | 29 | | | D41546P | | 31 | | 115-199 |
| 2027R | 24 | GL | BL | | 0-0 | 21-61-11 | D40670P | | 21 | | | D41546P | | 32 | | 001-099 |
| 2027R | 24 | GL | BL | | 0-0 | 21-61-11 | D41640J | | 30 | | | D41546P | | 32 | | 115-199 |
| 2028B | 24 | GL | BM | | 27-0 | 21-61-11 | D40670P | | 20 | | | D41546P | | 33 | | 001-099 |
| 2028B | 24 | GL | BM | | 46-0 | 21-61-11 | D41640J | | 31 | | | D41546P | | 33 | | 115-199 |
| 2028R | 24 | GL | BM | | 0-0 | 21-61-11 | D40670P | | 19 | | | D41546P | | 34 | | 001-099 |
| 2028R | 24 | GL | BM | | 0-0 | 21-61-11 | D41640J | | 32 | | | D41546P | | 34 | | 115-199 |
| 2029B | 24 | GL | AE | | 50-0 | SPARE | D41642J | | 39 | | | D40976P | | 49 | | 115-199 |
| 2029R | 24 | GL | AE | | 0-0 | SPARE | D41642J | | 40 | | | D40976P | | 50 | | 115-199 |
| 2030B | 24 | GL | CA | | 25-0 | 21-51-22 | D41546P | | 39 | | | D40666P | | 43 | | 001-099 |
| 2030B | 24 | GL | AF | | 46-0 | 21-51-22 | D41640J | | 33 | | | D41546P | | 39 | | 115-199 |
| 2030R | 24 | GL | CA | | 0-0 | 21-51-22 | D41546P | | 40 | | | D40666P | | 44 | | 001-099 |
| 2030R | 24 | GL | AF | | 0-0 | 21-51-22 | D41640J | | 34 | | | D41546P | | 40 | | 115-199 |
| 2031B | 24 | GL | BS | | 27-0 | 21-51-12 | D40064P | | 1 | | | D40844P | | 17 | | 001-099 |
| 2031B | 24 | GL | BS | | 46-0 | 21-51-12 | D40064P | | 1 | | | D41640J | | 35 | | 115-199 |
| 2031R | 24 | GL | BS | | 0-0 | 21-51-12 | D40064P | | 2 | | | D40844P | | 18 | | 001-099 |
| 2031R | 24 | GL | BS | | 0-0 | 21-51-12 | D40064P | | 2 | | | D41640J | | 36 | | 115-199 |
| 2033B | 24 | GL | DM | | 33-0 | 21-61-31 | D41640J | | 6 | | | D40844P | | 14 | | 001-099 |
| 2033R | 24 | GL | DM | | 0-0 | 21-61-31 | D41640J | | 5 | | | D40844P | | 13 | | 001-099 |
| 2034B | 24 | GL | DN | | 33-0 | 21-61-31 | D41640J | | 7 | | | D40844P | | 15 | | 001-099 |
| 2034R | 24 | GL | DN | | 0-0 | 21-61-31 | D41640J | | 8 | | | D40844P | | 16 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | |
| 2035B | 24 | GL | DH | | 25-0 | 21-51-22 | D40666P | | 54 | | D40064P | 10 | | | 001-099 |
| 2035R | 24 | GL | DH | | 0-0 | 21-51-22 | D40666P | | 55 | | D40064P | 59 | | | 001-099 |
| 2036B | 24 | GL | CT | | 34-0 | 21-65-12 | D42086P | | 54 | | D04648 | A | | | 001-099 |
| 2036B | 24 | GL | CT | | 33-0 | 21-65-12 | D42086P | | 54 | | D04648 | A | | | 115-199 |
| 2036R | 24 | GL | CT | | 0-0 | 21-65-12 | D42086P | | 55 | | SM00013 | | 9 | | ALL |
| 2037B | 24 | GL | CU | | 23-0 | 36-21-11 | D42086P | | 25 | | D40064P | 16 | | | 001-099 |
| 2037B | 24 | GL | CU | | 45-0 | 36-21-11 | D42086P | | 25 | | D40070J | 9 | | | 115-199 |
| 2037R | 24 | GL | CU | | 0-0 | 36-21-11 | D42086P | | 24 | | D40064P | 15 | | | 001-099 |
| 2037R | 24 | GL | CU | | 0-0 | 36-21-11 | D42086P | | 24 | | D40070J | 10 | | | 115-199 |
| 2038B | 24 | GL | DL | | 45-0 | 36-22-21 | D42086P | | 26 | | D41210J | 6 | | | 001-099 |
| 2038B | 24 | GL | CV | | 45-0 | 36-22-21 | D42086P | | 26 | | D41210J | 6 | | | 115-199 |
| 2038R | 24 | GL | DL | | 0-0 | 36-22-21 | D42086P | | 27 | | D41210J | 14 | | | 001-099 |
| 2038R | 24 | GL | CV | | 0-0 | 36-22-21 | D42086P | | 27 | | D41210J | 14 | | | 115-199 |
| 2039B | 24 | GL | AG | | 46-0 | 21-52-11 | D42086P | | 32 | | D40068J | 5 | | | 001-099 |
| 2039R | 24 | GL | AG | | 0-0 | 21-52-11 | D42086P | | 33 | | SM00003 | | 9 | | 001-099 |
| 2049B | 24 | GL | DA | | 25-0 | 21-51-22 | D40666P | | 31 | | D40064P | 4 | | | 001-099 |
| 2049B | 24 | GL | DA | | 46-0 | 21-51-22 | D41640J | | 37 | | D40064P | 4 | | | 115-199 |
| 2049R | 24 | GL | DA | | 0-0 | 21-51-22 | D40666P | | 32 | | D40064P | 5 | | | 001-099 |
| 2049R | 24 | GL | DA | | 0-0 | 21-51-22 | D41640J | | 38 | | D40064P | 5 | | | 115-199 |
| 2051B | 24 | GL | DB | | 53-0 | 21-51-22 | D40666P | | 33 | | D40068J | 2 | | | 001-099 |
| 2051B | 24 | GL | DB | | 13-0 | 21-51-22 | D41638J | | 17 | | D40068J | 2 | | | 115-199 |
| 2051R | 24 | GL | DB | | 0-0 | 21-51-22 | D40666P | | 34 | | D40068J | 3 | | | 001-099 |
| 2051R | 24 | GL | DB | | 0-0 | 21-51-22 | D41638J | | 18 | | D40068J | 3 | | | 115-199 |
| 2054B | 24 | GL | DC | | 54-0 | 21-51-22 | D40666P | | 10 | | D03012 | 1 | | | 001-099 |
| 2054B | 24 | GL | DC | | 13-0 | 21-51-22 | D41642J | | 23 | | D03012 | 1 | | | 115-199 |
| 2054R | 24 | GL | DC | | 0-0 | 21-51-22 | D40666P | | 9 | | D03012 | 2 | | | 001-099 |
| 2054R | 24 | GL | DC | | 0-0 | 21-51-22 | D41642J | | 24 | | D03012 | 2 | | | 115-199 |
| 2055B | 24 | GL | DE | | 27-0 | 21-61-11 | D41546P | | 44 | | D40670P | 37 | | | 001-099 |
| 2055B | 24 | GL | DE | | 46-0 | 21-61-11 | D41546P | | 44 | | D41640J | 39 | | | 115-199 |
| 2055R | 24 | GL | DE | | 0-0 | 21-61-11 | D41546P | | 43 | | D40670P | 36 | | | 001-099 |
| 2055R | 24 | GL | DE | | 0-0 | 21-61-11 | D41546P | | 43 | | D41640J | 40 | | | 115-199 |
| 3001B | 24 | GM | AV | | 53-0 | 21-51-22 | D40666P | | 14 | | D40068J | 33 | | | 001-099 |
| 3001B | 24 | GM | AV | | 13-0 | 21-51-22 | D41638J | | 19 | | D40068J | 33 | | | 115-199 |
| 3001R | 24 | GM | AV | | 0-0 | 21-51-22 | D40666P | | 13 | | D40068J | 34 | | | 001-099 |
| 3001R | 24 | GM | AV | | 0-0 | 21-51-22 | D41638J | | 20 | | D40068J | 34 | | | 115-199 |
| 3001Y | 24 | GM | AV | | 0-0 | 21-51-22 | D40666P | | 15 | | D40068J | 35 | | | 001-099 |
| 3001Y | 24 | GM | AV | | 0-0 | 21-51-22 | D41638J | | 21 | | D40068J | 35 | | | 115-199 |
| 3002B | 24 | GM | AW | | 53-0 | 21-51-22 | D40666P | | 17 | | D40068J | 27 | | | 001-099 |
| 3002B | 24 | GM | AW | | 13-0 | 21-51-22 | D41638J | | 22 | | D40068J | 27 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | |
| 3002R | 24 | | GM | AW | 0-0 | 21-51-22 | D40666P | | 16 | | D40068J | | 26 | | 001-099 |
| 3002R | 24 | | GM | AW | 0-0 | 21-51-22 | D41638J | | 23 | | D40068J | | 26 | | 115-199 |
| 3002Y | 24 | | GM | AW | 0-0 | 21-51-22 | D40666P | | 18 | | D40068J | | 28 | | 001-099 |
| 3002Y | 24 | | GM | AW | 0-0 | 21-51-22 | D41638J | | 24 | | D40068J | | 28 | | 115-199 |
| 3003B | 24 | | GM | AX | 53-0 | 21-51-22 | D40666P | | 19 | | D40068J | | 23 | | 001-099 |
| 3003B | 24 | | GM | AX | 13-0 | 21-51-22 | D41638J | | 25 | | D40068J | | 23 | | 115-199 |
| 3003R | 24 | | GM | AX | 0-0 | 21-51-22 | D40666P | | 20 | | D40068J | | 24 | | 001-099 |
| 3003R | 24 | | GM | AX | 0-0 | 21-51-22 | D41638J | | 26 | | D40068J | | 24 | | 115-199 |
| 3003Y | 24 | | GM | AX | 0-0 | 21-51-22 | D40666P | | 21 | | D40068J | | 25 | | 001-099 |
| 3003Y | 24 | | GM | AX | 0-0 | 21-51-22 | D41638J | | 27 | | D40068J | | 25 | | 115-199 |
| 3004B | 24 | | GM | AY | 53-0 | 21-51-22 | D40666P | | 23 | | D40068J | | 30 | | 001-099 |
| 3004B | 24 | | GM | AY | 13-0 | 21-51-22 | D41638J | | 28 | | D40068J | | 30 | | 115-199 |
| 3004R | 24 | | GM | AY | 0-0 | 21-51-22 | D40666P | | 22 | | D40068J | | 29 | | 001-099 |
| 3004R | 24 | | GM | AY | 0-0 | 21-51-22 | D41638J | | 29 | | D40068J | | 29 | | 115-199 |
| 3004Y | 24 | | GM | AY | 0-0 | 21-51-22 | D40666P | | 24 | | D40068J | | 31 | | 001-099 |
| 3004Y | 24 | | GM | AY | 0-0 | 21-51-22 | D41638J | | 30 | | D40068J | | 31 | | 115-199 |
| 3005B | 24 | | GM | BA | 53-0 | 21-51-22 | D40666P | | 29 | | D40068J | | 39 | | 001-099 |
| 3005B | 24 | | GM | BA | 13-0 | 21-51-22 | D41638J | | 31 | | D40068J | | 39 | | 115-199 |
| 3005R | 24 | | GM | BA | 0-0 | 21-51-22 | D40666P | | 28 | | D40068J | | 40 | | 001-099 |
| 3005R | 24 | | GM | BA | 0-0 | 21-51-22 | D41638J | | 32 | | D40068J | | 40 | | 115-199 |
| 3005Y | 24 | | GM | BA | 0-0 | 21-51-22 | D40666P | | 30 | | D40068J | | 41 | | 001-099 |
| 3005Y | 24 | | GM | BA | 0-0 | 21-51-22 | D41638J | | 33 | | D40068J | | 41 | | 115-199 |
| 3006B | 24 | | GM | BB | 53-0 | 21-51-22 | D40666P | | 26 | | D40068J | | 37 | | 001-099 |
| 3006B | 24 | | GM | BB | 13-0 | 21-51-22 | D41638J | | 34 | | D40068J | | 37 | | 115-199 |
| 3006R | 24 | | GM | BB | 0-0 | 21-51-22 | D40666P | | 25 | | D40068J | | 36 | | 001-099 |
| 3006R | 24 | | GM | BB | 0-0 | 21-51-22 | D41638J | | 35 | | D40068J | | 36 | | 115-199 |
| 3006Y | 24 | | GM | BB | 0-0 | 21-51-22 | D40666P | | 27 | | D40068J | | 38 | | 001-099 |
| 3006Y | 24 | | GM | BB | 0-0 | 21-51-22 | D41638J | | 36 | | D40068J | | 38 | | 115-199 |
| 3007B | 24 | | GM | BN | 27-0 | 21-61-11 | D40670P | | 9 | | D41546P | | 7 | | 001-099 |
| 3007B | 24 | | GM | BN | 46-0 | 21-61-11 | D41640J | | 41 | | D41546P | | 7 | | 115-199 |
| 3007R | 24 | | GM | BN | 0-0 | 21-61-11 | D40670P | | 8 | | D41546P | | 8 | | 001-099 |
| 3007R | 24 | | GM | BN | 0-0 | 21-61-11 | D41640J | | 42 | | D41546P | | 8 | | 115-199 |
| 3007Y | 24 | | GM | BN | 0-0 | 21-61-11 | D40670P | | 10 | | D41546P | | 6 | | 001-099 |
| 3007Y | 24 | | GM | BN | 0-0 | 21-61-11 | D41640J | | 43 | | D41546P | | 6 | | 115-199 |
| 3008B | 24 | | GM | BO | 27-0 | 21-61-21 | D40670P | | 24 | | D41546P | | 19 | | 001-099 |
| 3008B | 24 | | GM | BO | 46-0 | 21-61-21 | D41640J | | 44 | | D41546P | | 19 | | 115-199 |
| 3008R | 24 | | GM | BO | 0-0 | 21-61-21 | D40670P | | 23 | | D41546P | | 20 | | 001-099 |
| 3008R | 24 | | GM | BO | 0-0 | 21-61-21 | D41640J | | 45 | | D41546P | | 20 | | 115-199 |
| 3008Y | 24 | | GM | BO | 0-0 | 21-61-21 | D40670P | | 25 | | D41546P | | 18 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | |
| 3008Y | 24 | GM | BO | | 0-0 | 21-61-21 | D41640J | | 46 | | D41546P | | 18 | | 115-199 |
| 3009B | 24 | GM | BQ | | 27-0 | 21-61-31 | D40844P | | 10 | | D41546P | | 22 | | 001-099 |
| 3009B | 24 | GM | BQ | | 46-0 | 21-61-31 | D41640J | | 47 | | D41546P | | 22 | | 115-199 |
| 3009R | 24 | GM | BQ | | 0-0 | 21-61-31 | D40844P | | 11 | | D41546P | | 23 | | 001-099 |
| 3009R | 24 | GM | BQ | | 0-0 | 21-61-31 | D41640J | | 48 | | D41546P | | 23 | | 115-199 |
| 3009Y | 24 | GM | BQ | | 0-0 | 21-61-31 | D40844P | | 12 | | D41546P | | 21 | | 001-099 |
| 3009Y | 24 | GM | BQ | | 0-0 | 21-61-31 | D41640J | | 49 | | D41546P | | 21 | | 115-199 |
| 3010B | 24 | GM | BR | | 62-0 | 21-61-21 | D40670P | | 32 | | D02560 | | 5 | | 001-099 |
| 3010B | 24 | GM | BR | | 19-0 | 21-61-21 | D41642J | | 25 | | D02560 | | 5 | | 115-199 |
| 3010R | 24 | GM | BR | | 0-0 | 21-61-21 | D40670P | | 31 | | D02560 | | 4 | | 001-099 |
| 3010R | 24 | GM | BR | | 0-0 | 21-61-21 | D41642J | | 26 | | D02560 | | 4 | | 115-199 |
| 3010Y | 24 | GM | BR | | 0-0 | 21-61-21 | D40670P | | 33 | | D02560 | | 12 | | 001-099 |
| 3010Y | 24 | GM | BR | | 0-0 | 21-61-21 | D41642J | | 27 | | D02560 | | 12 | | 115-199 |
| 3011B | 24 | GM | BT | | 53-0 | 21-51-22 | D40666P | | 46 | | D40068J | | 7 | | 001-099 |
| 3011B | 24 | GM | BT | | 13-0 | 21-51-22 | D41638J | | 50 | | D40068J | | 7 | | 115-199 |
| 3011R | 24 | GM | BT | | 0-0 | 21-51-22 | D40666P | | 45 | | D40068J | | 6 | | 001-099 |
| 3011R | 24 | GM | BT | | 0-0 | 21-51-22 | D41638J | | 51 | | D40068J | | 6 | | 115-199 |
| 3011Y | 24 | GM | BT | | 0-0 | 21-51-22 | D40666P | | 47 | | D40068J | | 8 | | 001-099 |
| 3011Y | 24 | GM | BT | | 0-0 | 21-51-22 | D41638J | | 52 | | D40068J | | 8 | | 115-199 |
| 3017B | 24 | GM | CE | | 62-0 | 21-61-31 | D02574 | | 5 | | D40844P | | 3 | | 001-099 |
| 3017B | 24 | GM | CE | | 19-0 | 21-61-31 | D02574 | | 5 | | D41642J | | 28 | | 115-199 |
| 3017R | 24 | GM | CE | | 0-0 | 21-61-31 | D02574 | | 4 | | D40844P | | 2 | | 001-099 |
| 3017R | 24 | GM | CE | | 0-0 | 21-61-31 | D02574 | | 4 | | D41642J | | 29 | | 115-199 |
| 3017Y | 24 | GM | CE | | 0-0 | 21-61-31 | D02574 | | 12 | | D40844P | | 4 | | 001-099 |
| 3017Y | 24 | GM | CE | | 0-0 | 21-61-31 | D02574 | | 12 | | D41642J | | 30 | | 115-199 |
| 3018B | 24 | GM | CF | | 62-0 | 21-61-11 | D40670P | | 17 | | D02546 | | 5 | | 001-099 |
| 3018B | 24 | GM | CF | | 20-0 | 21-61-11 | D41642J | | 31 | | D02546 | | 5 | | 115-199 |
| 3018R | 24 | GM | CF | | 0-0 | 21-61-11 | D40670P | | 16 | | D02546 | | 4 | | 001-099 |
| 3018R | 24 | GM | CF | | 0-0 | 21-61-11 | D41642J | | 32 | | D02546 | | 4 | | 115-199 |
| 3018Y | 24 | GM | CF | | 0-0 | 21-61-11 | D40670P | | 18 | | D02546 | | 12 | | 001-099 |
| 3018Y | 24 | GM | CF | | 0-0 | 21-61-11 | D41642J | | 33 | | D02546 | | 12 | | 115-199 |
| 3020B | 24 | GM | CL | | 46-0 | 21-52-21 | D42086P | | 12 | | D40070J | | 12 | | 001-099 |
| 3020B | 24 | GM | CL | | 45-0 | 21-52-21 | D42086P | | 12 | | D40070J | | 12 | | 115-199 |
| 3020R | 24 | GM | CL | | 0-0 | 21-52-21 | D42086P | | 11 | | D40070J | | 11 | | ALL |
| 3020Y | 24 | GM | CL | | 0-0 | 21-52-21 | D42086P | | 13 | | D40070J | | 13 | | ALL |
| 3021B | 24 | GM | CM | | 46-0 | 21-52-21 | D42086P | | 15 | | D40070J | | 36 | | 001-099 |
| 3021B | 24 | GM | CM | | 45-0 | 21-52-21 | D42086P | | 15 | | D40070J | | 36 | | 115-199 |
| 3021R | 24 | GM | CM | | 0-0 | 21-52-21 | D42086P | | 16 | | D40070J | | 35 | | ALL |
| 3021Y | 24 | GM | CM | | 0-0 | 21-52-21 | D42086P | | 14 | | D40070J | | 37 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | | To | | | | | |
|------------|-------------|----|-------|---|---------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4106 | 286N4106 | | | E/E BAY TO R. W/B DISC-AIR COND. SYSTEM (continued) | | | | | | | | | | | | |
| 3022B | 24 | GM | CP | | 54-0 | 21-64-11 | D42086P | 42 | | | | D04654 | 3 | | | ALL |
| 3022R | 24 | GM | CP | | 0-0 | 21-64-11 | D42086P | 41 | | | | D04654 | 1 | | | ALL |
| 3022Y | 24 | GM | CP | | 0-0 | 21-64-11 | D42086P | 43 | | | | D04654 | 2 | | | ALL |
| 3023B | 24 | GM | CR | | 51-0 | 21-64-11 | D42086P | 45 | | | | D04656 | 3 | | | 001-099 |
| 3023B | 24 | GM | CR | | 50-0 | 21-64-11 | D42086P | 45 | | | | D04656 | 3 | | | 115-199 |
| 3023R | 24 | GM | CR | | 0-0 | 21-64-11 | D42086P | 44 | | | | D04656 | 1 | | | ALL |
| 3023Y | 24 | GM | CR | | 0-0 | 21-64-11 | D42086P | 46 | | | | D04656 | 2 | | | ALL |
| 3024B | 24 | GM | CS | | 53-0 | 21-64-11 | D42086P | 48 | | | | D04658 | 3 | | | ALL |
| 3024R | 24 | GM | CS | | 0-0 | 21-64-11 | D42086P | 47 | | | | D04658 | 1 | | | ALL |
| 3024Y | 24 | GM | CS | | 0-0 | 21-64-11 | D42086P | 49 | | | | D04658 | 2 | | | ALL |
| 4000B | 24 | GN | CN | | 46-0 | 21-52-31 | D42086P | 20 | | | | D40070J | 16 | | | 001-099 |
| 4000B | 24 | GN | CN | | 45-0 | 21-52-31 | D42086P | 20 | | | | D40070J | 16 | | | 115-199 |
| 4000G | 24 | GN | CN | | 0-0 | 21-52-31 | D42086P | 40 | | | | D40070J | 14 | | | ALL |
| 4000R | 24 | GN | CN | | 0-0 | 21-52-31 | D42086P | 19 | | | | D40070J | 15 | | | ALL |
| 4000Y | 24 | GN | CN | | 0-0 | 21-52-31 | D42086P | 21 | | | | D40070J | 17 | | | ALL |
| 5001B | 22 | GU | DD | | 46-0 | 32-42-11 | D41640J | 50 | | | | D40064P | 9 | | | 115-199 |
| 5001R | 22 | GU | DD | | 0-0 | 32-42-11 | D41640J | 51 | | | | D40064P | 8 | | | 115-199 |
| 5001Z | | | DD | | 0-0 | 32-42-11 | D41640J | 52 | | | | D40064P | 10 | | | 115-199 |
| A-BK | | | | | 0-0 | 30-71-21 | SP00420 | | | 9 | | B00118 | BLK | | | 115-199 |
| A-WT | | | | | 0-0 | 30-71-21 | B00118 | WHT | | | | GD02378 | AC.. | E | | 115-199 |
| H-GD | | | | | 0-0 | 30-71-21 | B00043 | =2 | | | | GD02380 | AC.. | E | | 115-199 |
| H-PR | | | | | 0-0 | 30-71-21 | SP00422 | | | 9 | | B00043 | =1 | | | 115-199 |
| I-BK | | | | | 0-0 | 30-71-21 | B00107 | BLK | | | | SP00401 | | 9 | | 115-199 |
| I-GD | | | | | 0-0 | 30-71-21 | B00085 | =2 | | | | SP00426 | | 9 | | 115-199 |
| J-BK | | | | | 0-0 | 30-71-21 | SP00426 | | | 9 | | B00117 | BLK | | | 115-199 |
| K-WT | | | | | 0-0 | 30-71-21 | B00107 | WHT | | | | GD02382 | AC.. | E | | 115-199 |
| L-WT | | | | | 0-0 | 30-71-21 | B00117 | WHT | | | | SP00401 | | 9 | | 115-199 |
| M-PR | | | | | 0-0 | 30-71-21 | SP00422 | | | 9 | | B00085 | =1 | | | 115-199 |
| YAAA | | | | | 0-0 | 36-11-22 | GD03071 | ST.. | E | * | | D41210J | S/R | | | 001-099 |
| YAAA | | | | | 0-0 | 36-11-22 | GD03096 | ST.. | E | * | | D41210J | S/R | | | 115-199 |
| YAAB | | | | | 0-0 | 21-51-21 | GD03071 | ST.. | E | * | | D40068J | S/R | | | 001-099 |
| YAAB | | | | | 0-0 | 21-51-21 | GD03096 | ST.. | E | * | | D40068J | S/R | | | 115-199 |
| YAAC | | | | | 0-0 | 21-52-31 | GD03071 | ST.. | E | * | | D40070J | S/R | | | 001-099 |
| YAAC | | | | | 0-0 | 21-52-31 | GD03096 | ST.. | E | * | | D40070J | S/R | | | 115-199 |
| YAAD | | | | | 0-0 | 21-51-23 | GD03071 | ST.. | E | * | | D41102J | S/R | | | 001-099 |
| YAAD | | | | | 0-0 | 21-51-23 | GD03096 | ST.. | E | * | | D41102J | S/R | | | 115-199 |
| W4108 | 286N4108 | | | THRUST REVERSER CONTROL SYNCH LOCK RIGHT ENGINE P37 TO WING BREAK/P10 | | | | | | | | | | | | |
| 0004 | 20 | GA | | | 2-0 | 78-36-21 | GD04058 | DC.. | 2 | | | D07710 | 12 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4108 | 286N4108 | | | | THRUST REVERSER CONTROL SYNCH LOCK RIGHT ENGINE P37 TO WING BREAK/P10 (continued) | | | | | | | | | | | |
| 0005 | 20 | GA | | | 2-0 | 78-36-21 | GD04058 | ST.. | 2 | | | D07710 | 11 | | | ALL |
| 0006 | 20 | GA | | | 2-0 | 78-36-21 | GD04058 | ST.. | 2 | | | D07710 | | | AV | ALL |
| 0007 | 20 | GA | | | 2-0 | 78-36-21 | GD04058 | ST.. | 2 | | | D07710 | 2 | | | ALL |
| 0008 | 16 | GA | | | 18-4 | 78-34-61 | D41478P | | 19 | 16 | | SP01942 | | 9 | | 001-002, 115-199 |
| 0008 | 16 | GA | | | 19-0 | 78-34-61 | D41478P | | 19 | 16 | | SP01942 | | 9 | | 003-099 |
| 0012 | 22 | GA | | | 35-2 | SPARE | D41478P | | 21 | | | D07710 | CAP | Y | | 001-002, 115-199 |
| 0012 | 22 | GA | | | 36-0 | 78-36-21 | D41478P | | 21 | | | D07710 | CAP | Y | | 003-099 |
| 1002 | 18 | GT | AN | | 35-2 | 78-34-21 | D07710 | | 5 | 18 | | D41478P | 31 | 18 | | 001-002, 115-199 |
| 1002 | 18 | GT | AN | | 36-0 | 78-34-21 | D07710 | | 5 | 18 | | D41478P | 31 | 18 | | 003-099 |
| 1002Z | | | AN | | 0-0 | 78-34-21 | D07710 | | 1 | | | D41478P | | | AA | ALL |
| 1004 | 18 | GT | AP | | 35-2 | 78-34-21 | D07710 | | 8 | 18 | | D41478P | 17 | 18 | | 001-002, 115-199 |
| 1004 | 18 | GT | AP | | 36-0 | 78-34-21 | D07710 | | 8 | 18 | | D41478P | 17 | 18 | | 003-099 |
| 1004Z | | | AP | | 0-0 | 78-34-21 | D07710 | | 9 | | | D41478P | | | AA | ALL |
| 1005 | 22 | GT | AR | | 35-2 | 78-36-21 | D07710 | | 3 | | | D41478P | 22 | | | 001-002, 115-199 |
| 1005 | 22 | GT | AR | | 36-0 | 78-36-21 | D07710 | | 3 | | | D41478P | 22 | | | 003-099 |
| 1005Z | | | AR | | 0-0 | 78-36-21 | D07710 | | | | AV | D41478P | DED | | | ALL |
| 2501B | 16 | GF | AF | | 49-10 | 78-34-61 | D41478P | | 8 | 16 | | D41458J | 4 | | | 001-002, 115-199 |
| 2501B | 16 | GF | AF | | 54-0 | 78-34-61 | D41478P | | 8 | 16 | | D41458J | 4 | | | 003-099 |
| 2501R | 16 | GF | AF | | 0-0 | 78-34-61 | D41478P | | 7 | 16 | | D41458J | 3 | | | ALL |
| 2501Z | | | AF | | 0-0 | 78-34-61 | D41478P | | 6 | | | D41458J | 5 | | | ALL |
| FRAA | | | | | 0-0 | 78-34-21 | D41478P | | 18 | | | D41478P | | | AA | ALL |
| FRAV | | | | | 0-0 | 78-36-21 | D07710 | | 4 | | | D07710 | | | AV | ALL |
| YAAA | | | | | 0-0 | 78-34-61 | D41458J | S/R | | | | GD04056 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4100

Page 15 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|--|-----------------|----|----|---------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4162 | | 286N4162 | | | P65 TO FORWARD CARGO BAY | | | | | | | | | | | |
| 0001 | | 18 | | GA | | 48-0 | 25-51-11 | D41926J | | 4 | | D02466 | | 1 | | 115-199 |
| 0002 | | 18 | | GA | | 48-0 | 25-51-11 | D41926J | | 6 | | D02466 | | 2 | | 115-199 |
| 0003 | | 18 | | GA | | 48-0 | 25-51-11 | D41926J | | 8 | | D02466 | | 3 | | 115-199 |
| 0004 | | 22 | | GA | | 48-0 | 25-51-11 | D41926J | | 11 | | D02466 | | 6 | | 115-199 |
| 0005 | | 18 | | GA | | 3-0 | 25-51-11 | D02466 | | 8 | | GD00134 | ST.. | E | | 115-199 |
| 0006 | | 22 | | GA | | 24-0 | 25-51-11 | D41926J | | 3 | | S10206 | CAP | Y | | 115-199 |
| 0007 | | 22 | | GA | | 24-0 | 25-51-11 | D41926J | | 9 | | S10206 | CAP | Y | | 115-199 |
| 0008 | | 22 | | GA | | 3-0 | 25-51-11 | D04746 | | 2 | | SM00002 | | 9 | | 115-199 |
| 0009 | | 22 | | GA | | 43-0 | 25-51-11 | D41926J | | 13 | | S10211 | CAP | Y | | 115-199 |
| 0010 | | 22 | | GA | | 32-0 | 25-51-11 | D41926J | | 5 | | S10209 | CAP | Y | | 115-199 |
| 0012 | | 18 | | GA | | 14-0 | 33-37-11 | C04048 | =L | D | | SM00001 | | 9 | | ALL |
| 0013 | | 18 | | GA | | 17-0 | 33-37-11 | SM00001 | | 9 | | L00233 | =P | C | * | ALL |
| 0014 | | 18 | | GA | | 25-0 | 33-37-11 | L00233 | =P | C | * | L00232 | =P | C | | ALL |
| 0015 | | 18 | | GA | | 10-0 | 33-37-11 | SM00001 | | 9 | | L00374 | =P | C | * | ALL |
| 0016 | | 18 | | GA | | 17-0 | 33-37-11 | L00374 | =P | C | * | L00235 | =P | C | * | ALL |
| 0017 | | 18 | | GA | | 22-0 | 33-37-11 | L00235 | =P | C | * | L00234 | =P | C | | ALL |
| 0018 | | 18 | | GA | | 7-0 | 33-37-11 | L00504 | =P | C | | SM00001 | | 9 | | ALL |
| 0019 | | 18 | | GA | | 4-0 | 33-37-11 | SP00201 | | 9 | | SM00001 | | 9 | | ALL |
| 0020 | | 18 | | GA | | 2-0 | 33-37-11 | L00504 | =G | C | | GD01821 | AC.. | E | | ALL |
| 0021 | | 18 | | GA | | 3-0 | 33-37-11 | L00233 | =G | C | | GD00870 | AC.. | E | | ALL |
| 0022 | | 18 | | GA | | 3-0 | 33-37-11 | L00232 | =G | C | | GD00877 | AC.. | E | | ALL |
| 0023 | | 18 | | GA | | 3-0 | 33-37-11 | L00374 | =G | C | | GD00875 | AC.. | E | | ALL |
| 0024 | | 18 | | GA | | 2-0 | 33-37-11 | L00235 | =G | C | | GD01735 | AC.. | E | | ALL |
| 0025 | | 18 | | GA | | 3-0 | 33-37-11 | L00234 | =G | C | | GD00874 | AC.. | E | | ALL |
| 0026 | | 16 | | GA | | 2-0 | 33-37-11 | D41188J | | 1 | | GD02348 | AC.. | E | | ALL |
| 0027 | | 16 | | GA | | 2-0 | 33-37-11 | D41188J | | 2 | | GD00878 | AC.. | E | | ALL |
| 0030 | | 20 | | GA | | 22-0 | 52-34-11 | D41926J | | 14 | | D02318 | | 1 | | ALL |
| 0031 | | 20 | | GA | | 22-0 | 52-34-11 | D41926J | | 15 | | D02318 | | 2 | | ALL |
| 0032 | | 20 | | GA | | 22-0 | 52-34-11 | D41926J | | 16 | | D02318 | | 3 | | ALL |
| 0033 | | 22 | | GA | | 30-0 | 52-34-11 | D41926J | | 7 | | SP00180 | | 9 | | ALL |
| 0034 | | 22 | | GA | | 21-0 | 52-34-11 | D41926J | | 17 | | D41188J | | 6 | | ALL |
| 0035 | | 20 | | GA | | 3-0 | 52-34-11 | D02318 | | 5 | | GD00039 | ST.. | E | | ALL |
| 0036 | | 14 | | GA | | 2-0 | 33-37-11 | D41926J | | 2 | | GD01416 | AC.. | E | | ALL |
| 0037 | | 14 | | GA | | 3-0 | 33-37-11 | D41926J | | 1 | | C04048 | =B | D | | 001-099 |
| 0037 | | 14 | | GA | | 4-0 | 33-37-11 | D41926J | | 1 | | C04048 | =B | D | | 115-199 |
| 0038 | | 14 | | GA | | 2-0 | 33-37-11 | C04048 | =B | D | | C04149 | =B | D | | ALL |
| 0039 | | 16 | | GA | | 22-0 | 33-37-11 | D41188J | | 3 | | C04149 | =L | D | | ALL |
| 0040 | | 22 | | GA | | 3-0 | 25-51-11 | D02466 | | 7 | | SM00002 | | 9 | | 115-199 |
| 0041 | | 22 | | GA | | 37-0 | 25-51-11 | D04746 | | 1 | | S10206 | CAP | Y | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4160

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4162 | 286N4162 | | | | P65 TO FORWARD CARGO BAY (continued) | | | | | | | | | | | | |
| 0042 | 22 | | GA | | 35-0 | 25-51-11 | S10206 | | CAP | Y | | SM00002 | | 9 | | 115-199 | |
| 0043 | 20 | | GA | | 24-0 | 25-51-11 | S10206 | | CAP | Y | | D41926J | | 18 | | 115-199 | |
| 0044 | 20 | | GA | | 24-0 | 25-51-11 | S10206 | | CAP | Y | | D41926J | | 19 | | 115-199 | |
| 0045 | 22 | | GA | | 14-0 | 52-34-11 | SP00182 | | | | 9 | D41188J | | 7 | | ALL | |
| 0062 | 20 | | GA | | 7-0 | 25-51-11 | S10211 | | CAP | Y | | GD00135 | DC.. | E | | 115-199 | |
| A-GA | | | | | 0-0 | 33-37-11 | L00381 | | =G | | | GD00156 | AC.. | E | | ALL | |
| A-PA | | | | | 0-0 | 33-37-11 | L00381 | | =P | | | SP00201 | | 9 | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W4160

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4202 | 286N4202 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2A | | | | | | | | | | | |
| 0001 | 20 | | GA | | 90-5 | SPARE | D41704P | | 9 | | D40346J | 29 | | | 001-099 |
| 0001 | 20 | | GA | | 92-0 | SPARE | D41704P | | 9 | | D40346J | 29 | | | 115-199 |
| 0002 | 22 | | GA | | 35-4 | SPARE | D41704P | | 8 | | D41610P | 13 | | | 001-099 |
| 0002 | 22 | | GA | | 36-0 | 29-11-12 | D41704P | | 8 | | D41610P | 13 | | | 115-199 |
| 0003 | 20 | | GA | | 87-4 | SPARE | D41704P | | 7 | | D40898P | 29 | | | 001-099 |
| 0003 | 20 | | GA | | 89-0 | SPARE | D41704P | | 7 | | D40898J | 32 | | | 115-199 |
| 0004 | 22 | | GA | | 87-4 | 28-26-11 | D41704P | | 12 | | D40898P | 21 | | | 001-099 |
| 0004 | 20 | | GA | | 89-0 | 28-26-11 | D41704P | | 12 | | D40898J | 21 | | | 115-199 |
| 0005 | 22 | | GA | | 87-4 | 28-26-11 | D41704P | | 13 | | D40898P | 13 | | | 001-099 |
| 0005 | 20 | | GA | | 89-0 | 28-26-11 | D41704P | | 13 | | D40898J | 13 | | | 115-199 |
| 0006 | 22 | | GA | | 87-4 | 28-26-11 | D41704P | | 14 | | D40898P | 14 | | | 001-099 |
| 0006 | 20 | | GA | | 89-0 | 28-26-11 | D41704P | | 14 | | D40898J | 14 | | | 115-199 |
| 0007 | 20 | | GA | | 86-3 | 27-62-11 | D40346J | | 4 | | D41612P | 1 | | | 001-099 |
| 0007 | 20 | | GA | | 88-0 | 27-62-11 | D40346J | | 4 | | D41612P | 1 | | | 115-199 |
| 0008 | 20 | | GA | | 25-11 | SPARE | D41704P | | 19 | | D41612P | 14 | | | 001-099 |
| 0008 | 20 | | GA | | 27-0 | SPARE | D41704P | | 19 | | D41612P | 14 | | | 115-199 |
| 0009 | 22 | | GA | | 25-5 | 30-32-11 | D41704P | | 20 | | D41698P | 31 | | | 001-099 |
| 0009 | 22 | | GA | | 26-0 | 30-32-11 | D41704P | | 20 | | D41698P | 32 | | | 115-199 |
| 0010 | 20 | | GA | | 35-4 | SPARE | D41610P | | 1 | | D41704P | 1 | | | 001-099 |
| 0010 | 20 | | GA | | 36-0 | 29-11-12 | D41610P | | 1 | | D41704P | 1 | | | 115-199 |
| 0011 | 22 | | GA | | 31-2 | 32-09-11 | D41610P | | 2 | | D41612P | 2 | | | 001-099 |
| 0011 | 20 | | GA | | 32-0 | 32-09-11 | D41610P | | 2 | | D41612P | 2 | | | 115-199 |
| 0012 | 22 | | GA | | 31-2 | 32-09-11 | D41610P | | 3 | | D41612P | 3 | | | 001-099 |
| 0012 | 20 | | GA | | 32-0 | 32-09-11 | D41610P | | 3 | | D41612P | 3 | | | 115-199 |
| 0013 | 22 | | GA | | 31-2 | 32-09-11 | D41610P | | 4 | | D41612P | 4 | | | 001-099 |
| 0013 | 20 | | GA | | 32-0 | 32-09-11 | D41610P | | 4 | | D41612P | 4 | | | 115-199 |
| 0014 | 22 | | GA | | 31-2 | 32-09-11 | D41610P | | 5 | | D41612P | 5 | | | 001-099 |
| 0014 | 20 | | GA | | 32-0 | 32-09-11 | D41610P | | 5 | | D41612P | 5 | | | 115-199 |
| 0015 | 22 | | GA | | 31-2 | 32-09-11 | D41610P | | 6 | | D41612P | 24 | | | 001-099 |
| 0015 | 22 | | GA | | 32-0 | 32-09-11 | D41610P | | 6 | | D41612P | 24 | | | 115-199 |
| 0016 | 22 | | GA | | 31-2 | 32-09-11 | D41610P | | 7 | | D41612P | 25 | | | 001-099 |
| 0016 | 20 | | GA | | 32-0 | 32-09-11 | D41610P | | 7 | | D41612P | 25 | | | 115-199 |
| 0017 | 22 | | GA | | 31-2 | 32-09-11 | D41610P | | 8 | | D41612P | 26 | | | 001-099 |
| 0017 | 20 | | GA | | 32-0 | 32-09-11 | D41610P | | 8 | | D41612P | 26 | | | 115-199 |
| 0018 | 20 | | GA | | 64-8 | 32-09-11 | D41610P | | 9 | | D40346J | 26 | | | 001-099 |
| 0018 | 20 | | GA | | 66-0 | 32-09-11 | D41610P | | 9 | | D40346J | 26 | | | 115-199 |
| 0019 | 22 | | GA | | 31-2 | 32-09-11 | D41610P | | 10 | | D41612P | 9 | | | 001-099 |
| 0019 | 20 | | GA | | 32-0 | 32-09-11 | D41610P | | 10 | | D41612P | 9 | | | 115-199 |
| 0020 | 22 | | GA | | 26-6 | 27-51-31 | D41704P | | 26 | | D41652P | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4202 | 286N4202 | | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2A (continued) | | | | | | | | | | | |
| 0020 | 22 | | GA | | 27-0 | 27-51-31 | | D41704P | 26 | | | D41652P | 18 | | | 115-199 |
| 0021 | 20 | | GA | | 90-5 | 29-31-11 | | D41704P | 3 | | | D40346J | 18 | | | 001-099 |
| 0021 | 20 | | GA | | 92-0 | 29-31-11 | | D41704P | 3 | | | D40346J | 18 | | | 115-199 |
| 0023 | 22 | | GA | | 64-8 | 27-11-11 | | D41610P | 17 | | | D40346J | 27 | | | 001-099 |
| 0023 | 22 | | GA | | 66-0 | 27-11-11 | | D41610P | 17 | | | D40346J | 27 | | | 115-199 |
| 0024 | 22 | | GA | | 64-8 | 27-11-11 | | D41610P | 18 | | | D40346J | 28 | | | 001-099 |
| 0024 | 22 | | GA | | 66-0 | 27-11-11 | | D41610P | 18 | | | D40346J | 28 | | | 115-199 |
| 0026 | 22 | | GA | | 36-2 | 28-21-23 | | D40898P | 11 | | | SP00512 | | 9 | | 001-099 |
| 0026 | 20 | | GA | | 37-0 | 28-21-23 | | D40898J | 11 | | | SP00512 | | 9 | | 115-199 |
| 0027 | 20 | | GA | | 36-2 | 28-21-23 | | D40898P | 12 | | | SP01012 | | 9 | | 001-099 |
| 0027 | 20 | | GA | | 37-0 | 28-21-23 | | D40898J | 12 | | | SP01012 | | 9 | | 115-199 |
| 0028 | 22 | | GA | | 31-2 | 32-09-11 | | D41610P | 14 | | | D41612P | 28 | | | 001-099 |
| 0028 | 20 | | GA | | 32-0 | 32-09-11 | | D41610P | 14 | | | D41612P | 28 | | | 115-199 |
| 0029 | 20 | | GA | | 35-4 | SPARE | | D41610P | 30 | | | D41704P | 29 | | | 001-099 |
| 0029 | 20 | | GA | | 36-0 | 32-09-11 | | D41610P | 30 | | | D41704P | 29 | | | 115-199 |
| 0031 | 24 | | GK | | 35-4 | 28-41-14 | | D41610P | 31 | | | D41704P | 15 | | | 001-099 |
| 0031 | 20 | | GA | | 36-0 | 28-41-14 | | D41610P | 31 | | | D41704P | 15 | | | 115-199 |
| 0032 | 24 | | GK | | 35-4 | 28-41-14 | | D41610P | 32 | | | D41704P | 16 | | | 001-099 |
| 0032 | 20 | | GA | | 36-0 | 28-41-14 | | D41610P | 32 | | | D41704P | 16 | | | 115-199 |
| 0033 | 24 | | GK | | 35-4 | 28-41-11 | | D41610P | 33 | | | D41704P | 17 | | | 001-099 |
| 0033 | 20 | | GA | | 36-0 | 28-41-11 | | D41610P | 33 | | | D41704P | 17 | | | 115-199 |
| 0034 | 24 | | GK | | 35-4 | 28-41-11 | | D41610P | 34 | | | D41704P | 18 | | | 001-099 |
| 0034 | 20 | | GA | | 36-0 | 28-41-11 | | D41610P | 34 | | | D41704P | 18 | | | 115-199 |
| 0042 | 20 | | GA | | 82-3 | 22-11-12 | | D41606P | 2 | | | D40346J | 24 | | | 001-099 |
| 0042 | 20 | | GA | | 84-0 | 22-11-12 | | D41606P | 2 | | | D40346J | 24 | | | 115-199 |
| 0043 | 20 | | GA | | 82-3 | 22-11-12 | | D41606P | 20 | | | D40346J | 22 | | | 001-099 |
| 0043 | 20 | | GA | | 84-0 | 22-11-12 | | D41606P | 20 | | | D40346J | 22 | | | 115-199 |
| 0044 | 22 | | GA | | 86-3 | 27-23-11 | | D41612P | 22 | | | D40346J | 1 | | | 001-099 |
| 0044 | 22 | | GA | | 88-0 | 27-23-11 | | D41612P | 22 | | | D40346J | 1 | | | 115-199 |
| 0045 | 22 | | GA | | 86-3 | 27-23-11 | | D41612P | 21 | | | D40346J | 6 | | | 001-099 |
| 0045 | 22 | | GA | | 88-0 | 27-23-11 | | D41612P | 21 | | | D40346J | 6 | | | 115-199 |
| 0046 | 22 | | GA | | 85-9 | 27-23-11 | | D41698P | 14 | | | D40346J | 16 | | | 001-099 |
| 0046 | 22 | | GA | | 87-0 | 27-23-11 | | D41698P | 14 | | | D40346J | 16 | | | 115-199 |
| 0048 | 22 | | GA | | 86-5 | 28-42-11 | | D41698P | 12 | | | D40348J | 4 | | | 001-099 |
| 0048 | 20 | | GA | | 88-0 | 28-42-11 | | D41698P | 12 | | | D40348J | 4 | | | 115-199 |
| 0049 | 22 | | GA | | 82-9 | 28-42-11 | | D41698P | 9 | | | D40898P | 20 | | | 001-099 |
| 0049 | 20 | | GA | | 84-0 | 28-42-11 | | D41698P | 9 | | | D40898J | 20 | | | 115-199 |
| 0050 | 24 | | GK | | 31-2 | 29-33-11 | | D41610P | 44 | | | D41612P | 10 | | | 001-099 |
| 0052 | 24 | | GK | | 15-3 | 30-31-11 | | D41612P | 52 | | | D41698P | 19 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4202 | 286N4202 | | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2A (continued) | | | | | | | | | | | |
| 0052 | 22 | GA | | | 16-0 | 30-31-11 | D41612P | 52 | | | | D41698P | 19 | | | 115-199 |
| 0053 | 24 | GK | | | 15-3 | 30-31-11 | D41612P | 53 | | | | D41698P | 20 | | | 001-099 |
| 0053 | 22 | GA | | | 16-0 | 30-31-11 | D41612P | 53 | | | | D41698P | 20 | | | 115-199 |
| 0054 | 24 | GK | | | 25-5 | 30-31-11 | D41704P | 21 | | | | D41698P | 21 | | | 001-099 |
| 0054 | 22 | GA | | | 26-0 | 30-31-11 | D41704P | 21 | | | | D41698P | 21 | | | 115-199 |
| 0055 | 24 | GK | | | 25-5 | 30-31-11 | D41704P | 22 | | | | D41698P | 22 | | | 001-099 |
| 0055 | 22 | GA | | | 26-0 | 30-31-11 | D41704P | 22 | | | | D41698P | 22 | | | 115-199 |
| 0056 | 22 | GA | | | 82-9 | 27-18-11 | D41698P | 8 | | | | D40898P | 5 | | | 001-099 |
| 0056 | 22 | GA | | | 84-0 | 27-18-11 | D41698P | 8 | | | | D40898J | 5 | | | 115-199 |
| 0057 | 22 | GA | | | 82-9 | SPARE | D41698P | 18 | | | | D40898P | 31 | | | 001-099 |
| 0057 | 22 | GA | | | 84-0 | SPARE | D41698P | 18 | | | | D40898J | 35 | | | 115-199 |
| 0058 | 24 | GK | | | 15-11 | 27-51-31 | D41652P | 17 | | | | D41698P | 30 | | | 001-099 |
| 0058 | 22 | GA | | | 16-0 | 27-51-31 | D41652P | 17 | | | | D41698P | 38 | | | 115-199 |
| 0059 | 22 | GA | | | 15-11 | SPARE | D41652P | 34 | | | | D41698P | 29 | | | 001-099 |
| 0059 | 22 | GA | | | 16-0 | SPARE | D41652P | 34 | | | | D41698P | 39 | | | 115-199 |
| 0060 | 24 | GK | | | 15-11 | 27-51-41 | D41652P | 20 | | | | D41698P | 1 | | | 001-099 |
| 0060 | 22 | GA | | | 16-0 | 27-51-41 | D41652P | 20 | | | | D41698P | 1 | | | 115-199 |
| 0061 | 24 | GK | | | 15-11 | 27-51-41 | D41652P | 21 | | | | D41698P | 2 | | | 001-099 |
| 0061 | 22 | GA | | | 16-0 | 27-51-41 | D41652P | 21 | | | | D41698P | 2 | | | 115-199 |
| 0062 | 24 | GK | | | 15-11 | 27-51-41 | D41652P | 22 | | | | D41698P | 3 | | | 001-099 |
| 0062 | 22 | GA | | | 16-0 | 27-51-41 | D41652P | 22 | | | | D41698P | 3 | | | 115-199 |
| 0063 | 24 | GK | | | 15-11 | 27-51-41 | D41652P | 23 | | | | D41698P | 4 | | | 001-099 |
| 0063 | 22 | GA | | | 16-0 | 27-51-41 | D41652P | 23 | | | | D41698P | 4 | | | 115-199 |
| 0064 | 24 | GK | | | 15-11 | 27-58-31 | D41652P | 3 | | | | D41698P | 23 | | | 001-099 |
| 0064 | 22 | GA | | | 16-0 | 27-58-31 | D41652P | 3 | | | | D41698P | 23 | | | 115-199 |
| 0066 | 20 | GA | | | 86-11 | SPARE | D41652P | 19 | | | | D40346J | 30 | | | 001-099 |
| 0066 | 20 | GA | | | 88-0 | SPARE | D41652P | 19 | | | | D40346J | 30 | | | 115-199 |
| 0068 | 22 | GA | | | 14-10 | 27-51-51 | D41612P | 46 | | | | D41652P | 25 | | | 001-099 |
| 0068 | 22 | GA | | | 15-0 | 27-51-51 | D41612P | 46 | | | | D41652P | 25 | | | 115-199 |
| 0069 | 22 | GA | | | 14-10 | SPARE | D41612P | 47 | | | | D41652P | 35 | | | 001-099 |
| 0069 | 22 | GA | | | 15-0 | SPARE | D41612P | 47 | | | | D41652P | 35 | | | 115-199 |
| 0070 | 24 | GK | | | 14-10 | 27-58-11 | D41612P | 30 | | | | D41652P | 24 | | | 001-099 |
| 0070 | 24 | GK | | | 15-0 | 27-58-11 | D41612P | 30 | | | | D41652P | 24 | | | 115-199 |
| 0077 | 22 | GA | | | 86-11 | 27-51-51 | D41612P | 23 | | | | D40348J | 7 | | | 001-099 |
| 0077 | 20 | GA | | | 88-0 | 27-51-51 | D41612P | 23 | | | | D40348J | 7 | | | 115-199 |
| 0078 | 22 | GA | | | 83-3 | 27-58-11 | D41612P | 6 | | | | D40898P | 17 | | | 001-099 |
| 0078 | 22 | GA | | | 85-0 | 27-58-11 | D41612P | 6 | | | | D40898J | 17 | | | 115-199 |
| 0079 | 22 | GA | | | 83-3 | 27-58-11 | D41612P | 7 | | | | D40898P | 18 | | | 001-099 |
| 0079 | 22 | GA | | | 85-0 | 27-58-11 | D41612P | 7 | | | | D40898J | 18 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4202 | 286N4202 | | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2A (continued) | | | | | | | | | | | |
| 0080 | 22 | | GA | | 83-3 | 27-58-11 | | D41612P | 8 | | | D40898P | 19 | | | 001-099 |
| 0080 | 22 | | GA | | 85-0 | 27-58-11 | | D41612P | 8 | | | D40898J | 19 | | | 115-199 |
| 0082 | 20 | | GA | | 7-0 | 28-22-11 | | S10712 | 1C | Z2 | | GD00262 | DC.. | E | | ALL |
| 0083 | 22 | | GA | | 20-0 | 28-22-11 | | S10712 | 1NO | Z2 | | D41704P | 24 | | | ALL |
| 0084 | 20 | | GA | | 43-8 | 33-41-11 | | D41612P | 20 | | | L00070 | 115V | E | | 001-099 |
| 0084 | 20 | | GA | | 45-0 | 33-41-11 | | D41612P | 20 | | | L00070 | 115V | E | | 115-199 |
| 0085 | 14 | | GA | | 2-4 | 33-41-11 | | L00070 | RTN | E | | GD00592 | AC.. | E | | 001-099 |
| 0085 | 14 | | GA | | 3-0 | 33-41-11 | | L00070 | RTN | E | | GD00592 | AC.. | E | | 115-199 |
| 0086 | 14 | | GA | | 2-3 | 33-41-11 | | L00070 | GND | E | | GD01665 | ST.. | E | | 001-099 |
| 0086 | 14 | | GA | | 3-0 | 33-41-11 | | L00070 | GND | E | | GD01665 | ST.. | E | | 115-199 |
| 0087 | 22 | | GA | | 15-11 | 27-51-51 | | D41698P | 7 | | | D41652P | 29 | | | 001-099 |
| 0087 | 22 | | GA | | 16-0 | 27-51-51 | | D41698P | 7 | | | D41652P | 29 | | | 115-199 |
| 0088 | 20 | | GA | | 27-3 | SPARE | | D41610P | 35 | | | D41606P | 3 | | | 001-099 |
| 0088 | 20 | | GA | | 28-0 | SPARE | | D41610P | 35 | | | D41606P | 3 | | | 115-199 |
| 0089 | 20 | | GA | | 27-3 | SPARE | | D41610P | 36 | | | D41606P | 4 | | | 001-099 |
| 0089 | 20 | | GA | | 28-0 | SPARE | | D41610P | 36 | | | D41606P | 4 | | | 115-199 |
| 0090 | 20 | | GA | | 64-8 | SPARE | | D41610P | 37 | | | D40346J | 32 | | | 001-099 |
| 0090 | 20 | | GA | | 66-0 | SPARE | | D41610P | 37 | | | D40346J | 32 | | | 115-199 |
| 0091 | 20 | | GA | | 82-3 | SPARE | | D41606P | 1 | | | D40346J | 33 | | | 001-099 |
| 0091 | 20 | | GA | | 66-0 | SPARE | | D41610P | 38 | | | D40346J | 33 | | | 115-199 |
| 0092 | 20 | | GA | | 64-8 | SPARE | | D41610P | 39 | | | D40346J | 34 | | | 001-099 |
| 0092 | 20 | | GA | | 66-0 | SPARE | | D41610P | 39 | | | D40346J | 34 | | | 115-199 |
| 0093 | 20 | | GA | | 65-4 | SPARE | | D41610P | 40 | | | D40348J | 8 | | | 001-099 |
| 0093 | 20 | | GA | | 67-0 | SPARE | | D41610P | 40 | | | D40348J | 8 | | | 115-199 |
| 0094 | 20 | | GA | | 61-8 | SPARE | | D41610P | 43 | | | D40898P | 27 | | | 001-099 |
| 0094 | 20 | | GA | | 63-0 | SPARE | | D41610P | 43 | | | D40898J | 31 | | | 115-199 |
| 0095 | 22 | | GA | | 14-10 | SPARE | | D41652P | 40 | | | D41612P | 48 | | | 001-099 |
| 0095 | 22 | | GA | | 15-0 | SPARE | | D41652P | 40 | | | D41612P | 48 | | | 115-199 |
| 0096 | 22 | | GA | | 14-10 | SPARE | | D41652P | 41 | | | D41612P | 49 | | | 001-099 |
| 0096 | 22 | | GA | | 15-0 | SPARE | | D41652P | 41 | | | D41612P | 49 | | | 115-199 |
| 0097 | 24 | | GK | | 26-6 | 27-51-31 | | D41652P | 30 | | | D41704P | 11 | | | 001-099 |
| 0097 | 22 | | GA | | 27-0 | 27-51-31 | | D41652P | 30 | | | D41704P | 11 | | | 115-199 |
| 0098 | 22 | | GA | | 26-6 | 27-51-31 | | D41652P | 31 | | | D41704P | 5 | | | 001-099 |
| 0098 | 22 | | GA | | 27-0 | 27-51-31 | | D41652P | 31 | | | D41704P | 5 | | | 115-199 |
| 1020 | 22 | | GT | A | 82-9 | 27-18-11 | | D41698P | 10 | | | D40898P | 36 | | | 001-099 |
| 1020 | 22 | | GT | A | 84-0 | 27-18-11 | | D41698P | 10 | | | D40898J | 36 | | | 115-199 |
| 1020Z | | | | A | 0-0 | 27-18-11 | | D41698P | 11 | | | D40898P | S/R | | | 001-099 |
| 1020Z | | | | A | 0-0 | 27-18-11 | | D41698P | 11 | | | D40898J | S/R | | | 115-199 |
| 2001B | 20 | | GB | AA | 57-0 | 32-09-11 | | D41610P | 12 | | | SP01254 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4202 | 286N4202 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2A (continued) | | | | | | | | | | | |
| 2001B | 20 | GB | AA | | 58-0 | 32-09-11 | D41610P | 12 | | | SP01254 | | 9 | | 115-199 |
| 2001R | 20 | GB | AA | | 0-0 | 32-09-11 | D41610P | 11 | | | SP01256 | | 9 | | ALL |
| 2002B | 22 | GB | AB | | 65-4 | 32-61-13 | D41610P | 25 | | | D40348J | 2 | | | 001-099 |
| 2002B | 22 | GB | AB | | 67-0 | 32-61-13 | D41610P | 25 | | | D40348J | 2 | | | 115-199 |
| 2002R | 22 | GB | AB | | 0-0 | 32-61-13 | D41610P | 24 | | | D40348J | 1 | | | ALL |
| 2003B | 22 | GB | AC | | 65-4 | 32-61-13 | D41610P | 27 | | | D40348J | 10 | | | 001-099 |
| 2003B | 22 | GB | AC | | 67-0 | 32-61-13 | D41610P | 27 | | | D40348J | 10 | | | 115-199 |
| 2003R | 22 | GB | AC | | 0-0 | 32-61-13 | D41610P | 26 | | | D40348J | 9 | | | ALL |
| 2004B | 24 | GL | AD | | 56-3 | 32-61-22 | D41610P | 19 | | | SM00002 | | 9 | | 001-099 |
| 2004B | 24 | GL | AD | | 58-0 | 32-61-22 | D41610P | 19 | | | SM00002 | | 9 | | 115-199 |
| 2004R | 24 | GL | AD | | 0-0 | 32-61-22 | D41610P | 20 | | | SM00001 | | 9 | | ALL |
| 2005B | 22 | GB | AE | | 61-8 | SPARE | D41610P | 16 | | | D40898P | 4 | | | 001-099 |
| 2005B | 22 | GB | AE | | 63-0 | 28-41-21 | D41610P | 16 | | | D40898J | 4 | | | 115-199 |
| 2005R | 22 | GB | AE | | 0-0 | SPARE | D41610P | 15 | | | D40898P | 3 | | | 001-099 |
| 2005R | 22 | GB | AE | | 0-0 | 28-41-21 | D41610P | 15 | | | D40898J | 3 | | | 115-199 |
| 2006B | 22 | GB | AF | | 61-8 | SPARE | D41610P | 42 | | | D40898P | 2 | | | 001-099 |
| 2006B | 22 | GB | AF | | 63-0 | 28-41-21 | D41610P | 42 | | | D40898J | 2 | | | 115-199 |
| 2006R | 22 | GB | AF | | 0-0 | SPARE | D41610P | 41 | | | D40898P | 1 | | | 001-099 |
| 2006R | 22 | GB | AF | | 0-0 | 28-41-21 | D41610P | 41 | | | D40898J | 1 | | | 115-199 |
| 2007B | 20 | GB | AG | | 82-3 | 22-11-11 | D41606P | 14 | | | D40346J | 14 | | | 001-099 |
| 2007B | 20 | GB | AG | | 84-0 | 22-11-11 | D41606P | 14 | | | D40346J | 14 | | | 115-199 |
| 2007R | 20 | GB | AG | | 0-0 | 22-11-11 | D41606P | 15 | | | D40346J | 15 | | | ALL |
| 2008B | 20 | GB | AH | | 82-3 | 22-13-11 | D41606P | 5 | | | D40346J | 20 | | | 001-099 |
| 2008B | 20 | GB | AH | | 84-0 | 22-13-11 | D41606P | 5 | | | D40346J | 20 | | | 115-199 |
| 2008R | 20 | GB | AH | | 0-0 | 22-13-11 | D41606P | 6 | | | D40346J | 17 | | | ALL |
| 2009B | 22 | GB | AI | | 82-9 | 27-18-11 | D41698P | 5 | | | D40898P | 6 | | | 001-099 |
| 2009B | 22 | GB | AI | | 84-0 | 27-18-11 | D41698P | 5 | | | D40898J | 6 | | | 115-199 |
| 2009R | 22 | GB | AI | | 0-0 | 27-18-11 | D41698P | 6 | | | D40898P | 7 | | | 001-099 |
| 2009R | 22 | GB | AI | | 0-0 | 27-18-11 | D41698P | 6 | | | D40898J | 7 | | | 115-199 |
| 2011B | 22 | GB | AK | | 83-10 | 27-51-41 | D41652P | 27 | | | D40898P | 16 | | | 001-099 |
| 2011B | 22 | GB | AK | | 85-0 | 27-51-41 | D41652P | 27 | | | D40898J | 16 | | | 115-199 |
| 2011R | 22 | GB | AK | | 0-0 | 27-51-41 | D41652P | 28 | | | D40898P | 15 | | | 001-099 |
| 2011R | 22 | GB | AK | | 0-0 | 27-51-41 | D41652P | 28 | | | D40898J | 15 | | | 115-199 |
| 2012B | 24 | GL | AL | | 31-2 | SPARE | D41612P | 45 | | | D41610P | 28 | | | 001-099 |
| 2012B | 22 | GB | AL | | 32-0 | SPARE | D41612P | 45 | | | D41610P | 28 | | | 115-199 |
| 2012R | 24 | GL | AL | | 0-0 | SPARE | D41612P | 27 | | | D41610P | 29 | | | 001-099 |
| 2012R | 22 | GB | AL | | 0-0 | SPARE | D41612P | 27 | | | D41610P | 29 | | | 115-199 |
| 2013B | 20 | GB | EB | | 85-9 | 29-31-11 | D40346J | 25 | | | D41698P | 16 | | | 001-099 |
| 2013B | 20 | GB | EB | | 87-0 | 29-31-11 | D40346J | 25 | | | D41698P | 16 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4202 | 286N4202 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2A (continued) | | | | | | | | | | | |
| 2013R | 20 | GB | EB | | 0-0 | 29-31-11 | D40346J | 23 | | | D41698P | 17 | | | ALL |
| 2501B | 22 | GU | BA | | 61-8 | 28-21-21 | D41610P | 22 | | | D40898P | 9 | | | 001-099 |
| 2501B | 22 | GU | BA | | 63-0 | 28-21-21 | D41610P | 22 | | | D40898J | 9 | | | 115-199 |
| 2501R | 22 | GU | BA | | 0-0 | 28-21-21 | D41610P | 21 | | | D40898P | 8 | | | 001-099 |
| 2501R | 22 | GU | BA | | 0-0 | 28-21-21 | D41610P | 21 | | | D40898J | 8 | | | 115-199 |
| 2501Z | | | BA | | 0-0 | 28-21-21 | D41610P | 23 | | | D40898P | 10 | | | 001-099 |
| 2501Z | | | BA | | 0-0 | 28-21-21 | D41610P | 23 | | | D40898J | 10 | | | 115-199 |
| 2502B | 20 | GF | AM | | 8-0 | 32-61-22 | SM00002 | | 9 | | D40380J | 2 | | | 001-099 |
| 2502B | 20 | GF | AJ | | 9-0 | 32-61-22 | SM00002 | | 9 | | D40380J | 2 | | | 115-199 |
| 2502R | 20 | GF | AM | | 0-0 | 32-61-22 | SM00001 | | 9 | | D40380J | 1 | | | 001-099 |
| 2502R | 20 | GF | AJ | | 0-0 | 32-61-22 | SM00001 | | 9 | | D40380J | 1 | | | 115-199 |
| 2502Z | | | AM | | 0-0 | 32-61-22 | SM00002 | | 9 | | D40380J | DED | | | 001-099 |
| 2502Z | | | AJ | | 0-0 | 32-61-22 | SM00002 | | 9 | | D40380J | DED | | | 115-199 |
| 3001B | 16 | GC | CA | | 91-1 | 28-22-11 | D41704P | 6 | | | D40348J | 3 | | | 001-099 |
| 3001B | 16 | GC | CA | | 93-0 | 28-22-11 | D41704P | 6 | | | D40348J | 3 | | | 115-199 |
| 3001R | 16 | GC | CA | | 0-0 | 28-22-11 | D41704P | 4 | | | D40348J | 5 | | | ALL |
| 3001Y | 16 | GC | CA | | 0-0 | 28-22-11 | D41704P | 10 | | | D40348J | 6 | | | ALL |
| 3002B | 18 | GC | AJ | | 87-4 | 28-22-11 | D41704P | 23 | 18 | | SP05012 | 9 | | | 001-099 |
| 3002B | 18 | GC | AM | | 89-0 | 28-22-11 | D41704P | 23 | 18 | | SP05012 | 9 | | | 115-199 |
| 3002R | 18 | GC | AJ | | 0-0 | 28-22-11 | D41704P | 25 | 18 | | SP05008 | 9 | | | 001-099 |
| 3002R | 18 | GC | AM | | 0-0 | 28-22-11 | D41704P | 25 | 18 | | SP05008 | 9 | | | 115-199 |
| 3002Y | 18 | GC | AJ | | 0-0 | 28-22-11 | D41704P | 27 | 18 | | SP05010 | 9 | | | 001-099 |
| 3002Y | 18 | GC | AM | | 0-0 | 28-22-11 | D41704P | 27 | 18 | | SP05010 | 9 | | | 115-199 |
| 3003B | 20 | GC | CC | | 82-3 | 22-13-11 | D41606P | 10 | | | D40346J | 12 | | | 001-099 |
| 3003B | 20 | GC | CC | | 84-0 | 22-13-11 | D41606P | 10 | | | D40346J | 12 | | | 115-199 |
| 3003R | 20 | GC | CC | | 0-0 | 22-13-11 | D41606P | 11 | | | D40346J | 11 | | | ALL |
| 3003Y | 20 | GC | CC | | 0-0 | 22-13-11 | D41606P | 12 | | | D40346J | 13 | | | ALL |
| 3004B | 20 | GC | CD | | 82-3 | 22-13-11 | D41606P | 7 | | | D40346J | 9 | | | 001-099 |
| 3004B | 20 | GC | CD | | 84-0 | 22-13-11 | D41606P | 7 | | | D40346J | 9 | | | 115-199 |
| 3004R | 20 | GC | CD | | 0-0 | 22-13-11 | D41606P | 8 | | | D40346J | 8 | | | ALL |
| 3004Y | 20 | GC | CD | | 0-0 | 22-13-11 | D41606P | 9 | | | D40346J | 10 | | | ALL |
| 4001B | 22 | GD | EA | | 83-10 | 27-51-41 | D41652P | 13 | | | D40898P | 23 | | | 001-099 |
| 4001B | 22 | GD | EA | | 85-0 | 27-51-41 | D41652P | 13 | | | D40898J | 23 | | | 115-199 |
| 4001G | 22 | GD | EA | | 0-0 | 27-51-41 | D41652P | 14 | | | D40898P | 25 | | | 001-099 |
| 4001G | 22 | GD | EA | | 0-0 | 27-51-41 | D41652P | 14 | | | D40898J | 25 | | | 115-199 |
| 4001R | 22 | GD | EA | | 0-0 | 27-51-41 | D41652P | 15 | | | D40898P | 22 | | | 001-099 |
| 4001R | 22 | GD | EA | | 0-0 | 27-51-41 | D41652P | 15 | | | D40898J | 22 | | | 115-199 |
| 4001Y | 22 | GD | EA | | 0-0 | 27-51-41 | D41652P | 16 | | | D40898P | 24 | | | 001-099 |
| 4001Y | 22 | GD | EA | | 0-0 | 27-51-41 | D41652P | 16 | | | D40898J | 24 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4202 | 286N4202 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2A (continued) | | | | | | | | | | | |
| YAAA | | | | | 0-0 | 27-58-11 | D40898P | | S/R | | GD02585 | ST.. | E | * | 001-099 |
| YAAA | | | | | 0-0 | 27-51-41 | GD02585 | | ST.. | E | | S/R | | | 115-199 |
| YAAB | | | | | 0-0 | 32-61-22 | D40380J | | S/R | | GD02585 | ST.. | E | * | 001-099 |
| YAAB | | | | | 0-0 | 32-61-12 | GD02585 | | ST.. | E | | S/R | | | 115-199 |
| W4204 | 286N4204 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2B | | | | | | | | | | | |
| 0001 | 22 | | GA | | 136-0 | 27-38-11 | D41628P | | 18 | | D40120P | | 1 | | 001-099 |
| 0001 | 22 | | GA | | 137-0 | 27-38-11 | D41628P | | 18 | | D40120P | | 1 | | 115-199 |
| 0002 | 20 | | GA | | 128-0 | 33-45-11 | D40120P | | 8 | | D41618P | | 8 | | 001-099 |
| 0002 | 20 | | GA | | 128-0 | 33-45-11 | D41618P | | 1 | | D40120P | | 8 | | 115-199 |
| 0003 | 24 | | GK | | 31-0 | 52-71-11 | D41618P | | 22 | | D41628P | | 5 | | 001-099 |
| 0003 | 24 | | GK | | 32-0 | 52-71-11 | D41618P | | 22 | | D41628P | | 5 | | 115-199 |
| 0004 | 24 | | GK | | 31-0 | 52-71-11 | D41618P | | 24 | | D41628P | | 6 | | 001-099 |
| 0004 | 24 | | GK | | 32-0 | 52-71-11 | D41618P | | 24 | | D41628P | | 6 | | 115-199 |
| 0005 | 24 | | GK | | 31-0 | 52-71-11 | D41618P | | 2 | | D41628P | | 7 | | 001-099 |
| 0005 | 24 | | GK | | 32-0 | 52-71-11 | D41618P | | 25 | | D41628P | | 7 | | 115-199 |
| 0006 | 24 | | GK | | 31-0 | 52-71-11 | D41618P | | 3 | | D41628P | | 8 | | 001-099 |
| 0006 | 24 | | GK | | 32-0 | 52-71-11 | D41618P | | 26 | | D41628P | | 8 | | 115-199 |
| 0007 | 24 | | GK | | 31-0 | 52-71-11 | D41618P | | 4 | | D41628P | | 9 | | 001-099 |
| 0007 | 24 | | GK | | 32-0 | 52-71-11 | D41618P | | 27 | | D41628P | | 9 | | 115-199 |
| 0008 | 24 | | GK | | 31-0 | 52-71-11 | D41618P | | 5 | | D41628P | | 10 | | 001-099 |
| 0008 | 24 | | GK | | 32-0 | 52-71-11 | D41618P | | 28 | | D41628P | | 10 | | 115-199 |
| 0009 | 22 | | GA | | 32-0 | SPARE | D41618P | | 29 | | D41628P | | 11 | | 115-199 |
| 0010 | 22 | | GA | | 32-0 | SPARE | D41618P | | 30 | | D41628P | | 12 | | 115-199 |
| 0011 | 22 | | GA | | 91-0 | SPARE | D41626P | | 13 | | D40302J | | 10 | | 001-099 |
| 0011 | 22 | | GA | | 32-0 | SPARE | D41618P | | 31 | | D41628P | | 13 | | 115-199 |
| 0012 | 22 | | GA | | 32-0 | SPARE | D41618P | | 32 | | D41628P | | 14 | | 115-199 |
| 0013 | 22 | | GA | | 32-0 | SPARE | D41618P | | 33 | | D41628P | | 15 | | 115-199 |
| 0016 | 24 | | GK | | 31-0 | 28-41-13 | D41618P | | 18 | | D41628P | | 1 | | 001-099 |
| 0016 | 22 | | GA | | 32-0 | 28-41-13 | D41618P | | 18 | | D41628P | | 1 | | 115-199 |
| 0017 | 24 | | GK | | 31-0 | 28-41-11 | D41618P | | 19 | | D41628P | | 2 | | 001-099 |
| 0017 | 22 | | GA | | 32-0 | 28-41-11 | D41618P | | 19 | | D41628P | | 2 | | 115-199 |
| 0023 | 22 | | GA | | 136-0 | 27-23-11 | D41628P | | 31 | | D40120P | | 4 | | 001-099 |
| 0023 | 22 | | GA | | 137-0 | 27-23-11 | D41628P | | 31 | | D40120P | | 4 | | 115-199 |
| 0024 | 22 | | GA | | 136-0 | 27-23-11 | D41628P | | 32 | | D40120P | | 5 | | 001-099 |
| 0024 | 22 | | GA | | 137-0 | 27-23-11 | D41628P | | 32 | | D40120P | | 5 | | 115-199 |
| 0028 | 24 | | GK | | 136-0 | 27-28-11 | D41628P | | 23 | | D40142J | | 1 | | 001-099 |
| 0028 | 22 | | GA | | 137-0 | 27-28-11 | D41628P | | 23 | | D40142J | | 1 | | 115-199 |
| 0031 | 22 | | GA | | 136-0 | 27-28-13 | D41628P | | 26 | | D40142J | | 6 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4204 | 286N4204 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2B (continued) | | | | | | | | | | | |
| 0031 | 22 | | GA | | 137-0 | 27-28-13 | D41628P | 26 | | | D40142J | 6 | | | 115-199 |
| 0032 | 22 | | GA | | 136-0 | 27-28-13 | D41628P | 27 | | | D40142J | 9 | | | 001-099 |
| 0032 | 22 | | GA | | 137-0 | 27-28-13 | D41628P | 27 | | | D40142J | 9 | | | 115-199 |
| 0034 | 20 | | GA | | 91-0 | 33-42-11 | D41626P | 4 | | | D40302J | 3 | | | 001-099 |
| 0034 | 20 | | GA | | 89-0 | 33-42-11 | D41626P | 4 | | | D40302J | 3 | | | 115-199 |
| 0035 | 20 | | GA | | 91-0 | 33-42-11 | D41626P | 5 | | | D40302J | 4 | | | 001-099 |
| 0035 | 20 | | GA | | 89-0 | 33-42-11 | D41626P | 5 | | | D40302J | 4 | | | 115-199 |
| 0037 | 20 | | GA | | 91-0 | 33-43-11 | D41626P | 7 | | | D40302J | 2 | | | 001-099 |
| 0037 | 20 | | GA | | 89-0 | 33-43-11 | D41626P | 7 | | | D40302J | 2 | | | 115-199 |
| 0038 | 20 | | GA | | 91-0 | 33-44-21 | D41626P | 8 | | | D40302J | 5 | | | 001-099 |
| 0038 | 20 | | GA | | 89-0 | 33-44-21 | D41626P | 8 | | | D40302J | 5 | | | 115-199 |
| 0039 | 22 | | GA | | 87-0 | 27-81-31 | D41630P | 7 | | | D40302J | 12 | | | 001-099 |
| 0039 | 22 | | GA | | 86-0 | 27-81-31 | D41630P | 7 | | | D40302J | 12 | | | 115-199 |
| 0040 | 22 | | GA | | 137-0 | 27-23-21 | D41630P | 8 | | | D40142J | 10 | | | 001-099 |
| 0040 | 22 | | GA | | 139-0 | 27-23-21 | D41630P | 8 | | | D40142J | 10 | | | 115-199 |
| 0041 | 22 | | GA | | 137-0 | 27-23-21 | D41630P | 9 | | | D40142J | 11 | | | 001-099 |
| 0041 | 22 | | GA | | 139-0 | 27-23-21 | D41630P | 9 | | | D40142J | 11 | | | 115-199 |
| 0042 | 22 | | GA | | 138-0 | 27-23-21 | D41630P | 10 | | | D40120P | 6 | | | 001-099 |
| 0042 | 22 | | GA | | 139-0 | 27-23-21 | D41630P | 10 | | | D40120P | 6 | | | 115-199 |
| 0043 | 22 | | GA | | 138-0 | 27-23-21 | D41630P | 11 | | | D40120P | 7 | | | 001-099 |
| 0043 | 22 | | GA | | 139-0 | 27-23-21 | D41630P | 11 | | | D40120P | 7 | | | 115-199 |
| 0044 | 22 | | GA | | 136-0 | SPARE | D41628P | 33 | | | D40120P | 9 | | | 001-099 |
| 0044 | 22 | | GA | | 137-0 | SPARE | D41628P | 33 | | | D40120P | 9 | | | 115-199 |
| 0045 | 22 | | GA | | 136-0 | SPARE | D41628P | 34 | | | D40120P | 10 | | | 001-099 |
| 0045 | 22 | | GA | | 137-0 | SPARE | D41628P | 34 | | | D40120P | 10 | | | 115-199 |
| 0046 | 22 | | GA | | 136-0 | SPARE | D41628P | 35 | | | D40142J | 12 | | | 001-099 |
| 0046 | 22 | | GA | | 137-0 | SPARE | D41628P | 35 | | | D40142J | 12 | | | 115-199 |
| 0047 | 22 | | GA | | 136-0 | SPARE | D41628P | 36 | | | D40142J | 13 | | | 001-099 |
| 0047 | 22 | | GA | | 137-0 | SPARE | D41628P | 36 | | | D40142J | 13 | | | 115-199 |
| 0048 | 22 | | GA | | 37-0 | SPARE | D41618P | 2 | | | D41626P | 9 | | | 115-199 |
| 0049 | 22 | | GA | | 37-0 | SPARE | D41618P | 3 | | | D41626P | 10 | | | 115-199 |
| 0050 | 22 | | GA | | 76-0 | SPARE | D41618P | 4 | | | D40302J | 6 | | | 115-199 |
| 0051 | 22 | | GA | | 76-0 | SPARE | D41618P | 5 | | | D40302J | 7 | | | 115-199 |
| 0052 | 22 | | GA | | 33-0 | SPARE | D41618P | 6 | | | D41630P | 12 | | | 001-099 |
| 0052 | 22 | | GA | | 34-0 | SPARE | D41618P | 6 | | | D41630P | 12 | | | 115-199 |
| 0056 | 20 | | GA | | 2-0 | 27-23-11 | D02916 | 1 | | | GD00930 | DC.. | E | | ALL |
| 0057 | 20 | | GA | | 2-0 | 27-23-11 | D02916 | 9 | | | GD00930 | DC.. | E | | ALL |
| 0139 | 22 | | GA | | 14-0 | 27-23-11 | D41628P | 12 | | | SM00001 | | 9 | | 001-099 |
| 0139 | 22 | | GA | | 11-0 | 27-23-11 | D41628P | 37 | | | SM00001 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4204 | 286N4204 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2B (continued) | | | | | | | | | | | |
| 0140 | 20 | | GA | | 110-0 | 27-23-11 | D40574P | 6 | | | D02916 | 3 | | | 001-099 |
| 0140 | 20 | | GA | | 114-0 | 27-23-11 | D41630P | 13 | | | D02916 | 3 | | | 115-199 |
| 0141 | 20 | | GA | | 110-0 | 27-23-11 | D40574P | 5 | | | D02916 | 2 | | | 001-099 |
| 0141 | 20 | | GA | | 114-0 | 27-23-11 | D41630P | 14 | | | D02916 | 2 | | | 115-199 |
| 0142 | 22 | | GA | | 11-0 | 27-23-11 | D40574P | 4 | | | SM00001 | 9 | | | 001-099 |
| 0142 | 22 | | GA | | 12-0 | 27-23-11 | D41630P | 15 | | | SM00001 | 9 | | | 115-199 |
| 0143 | 20 | | GA | | 100-0 | 27-23-11 | SM00001 | | 9 | | D02916 | 10 | | | 001-099 |
| 0143 | 20 | | GA | | 103-0 | 27-23-11 | SM00001 | | 9 | | D02916 | 10 | | | 115-199 |
| 0183 | 22 | | GA | | 31-0 | SPARE | D41618P | 16 | | | D41628P | 4 | | | 001-099 |
| 0183 | 22 | | GA | | 32-0 | SPARE | D41618P | 37 | | | D41628P | 4 | | | 115-199 |
| 0184 | 22 | | GA | | 31-0 | SPARE | D41618P | 15 | | | D41628P | 3 | | | 001-099 |
| 0184 | 22 | | GA | | 32-0 | SPARE | D41618P | 36 | | | D41628P | 3 | | | 115-199 |
| 0192 | 22 | | GA | | 83-0 | SPARE | D40574P | 3 | | | D40302J | 8 | | | 001-099 |
| 0193 | 22 | | GA | | 83-0 | SPARE | D40574P | 7 | | | D40302J | 9 | | | 001-099 |
| 0202 | 22 | | GA | | 27-0 | 29-11-12 | D41626P | 2 | | | D41628P | 39 | | | 001-099 |
| 0203 | 22 | | GA | | 27-0 | 29-11-12 | D41626P | 12 | | | D41628P | 38 | | | 001-099 |
| 0222 | 22 | | GA | | 27-0 | 29-11-12 | D41628P | 15 | | | D41626P | 1 | | | 001-099 |
| 1001 | 20 | | GT | BA | 138-0 | 27-21-11 | D40007P | 1 | | | D40142J | 15 | | | 001-099 |
| 1001 | 20 | | GT | BA | 139-0 | 27-21-11 | D40007P | 1 | | | D40142J | 15 | | | 115-199 |
| 1001Z | | | | BA | 0-0 | 27-21-11 | D40007P | DED | | | D40142J | DED | | | ALL |
| 1002 | 20 | | GT | BB | 138-0 | 27-21-11 | D40007P | 2 | | | D40142J | 4 | | | 001-099 |
| 1002 | 20 | | GT | BB | 139-0 | 27-21-11 | D40007P | 2 | | | D40142J | 4 | | | 115-199 |
| 1002Z | | | | BB | 0-0 | 27-21-11 | D40007P | DED | | | D40142J | DED | | | ALL |
| 1004 | 22 | | GT | A | 136-0 | 27-28-11 | D41628P | 16 | | | D40142J | 16 | | | 001-099 |
| 1004 | 22 | | GT | A | 137-0 | 27-28-11 | D41628P | 16 | | | D40142J | 16 | | | 115-199 |
| 1004Z | | | | A | 0-0 | 27-28-11 | D41628P | 17 | | | D40142J | 17 | | | ALL |
| 1025 | 22 | | GT | B | 136-0 | 27-38-11 | D41628P | 46 | | | D40120P | 12 | | | 001-099 |
| 1025 | 22 | | GT | B | 137-0 | 27-38-11 | D41628P | 46 | | | D40120P | 12 | | | 115-199 |
| 1025Z | | | | B | 0-0 | 27-38-11 | D41628P | 47 | | | D40120P | 13 | | | ALL |
| 2001B | 22 | | GB | AA | 136-0 | 27-38-11 | D41628P | 20 | | | D40120P | 3 | | | 001-099 |
| 2001B | 22 | | GB | AA | 137-0 | 27-38-11 | D41628P | 20 | | | D40120P | 3 | | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 27-38-11 | D41628P | 19 | | | D40120P | 2 | | | ALL |
| 2002B | 24 | | GL | AB | 136-0 | 27-28-13 | D41628P | 28 | | | D40142J | 7 | | | 001-099 |
| 2002B | 22 | | GB | AB | 137-0 | 27-28-13 | D41628P | 28 | | | D40142J | 7 | | | 115-199 |
| 2002R | 24 | | GL | AB | 0-0 | 27-28-13 | D41628P | 29 | | | D40142J | 8 | | | 001-099 |
| 2002R | 22 | | GB | AB | 0-0 | 27-28-13 | D41628P | 29 | | | D40142J | 8 | | | 115-199 |
| 2003B | 24 | | GL | AC | 136-0 | 27-28-11 | D41628P | 24 | | | D40142J | 2 | | | 001-099 |
| 2003B | 22 | | GB | AC | 137-0 | 27-28-11 | D41628P | 24 | | | D40142J | 2 | | | 115-199 |
| 2003R | 24 | | GL | AC | 0-0 | 27-28-11 | D41628P | 25 | | | D40142J | 3 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|--------|-------|---------|------|--------|--|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4204 | 286N4204 | | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - L2B (continued) | | | | | | | | | | | | |
| 2003R | 22 | GB | AC | | 0-0 | 27-28-11 | | D41628P | 25 | | | D40142J | 3 | | | 115-199 | |
| 2005B | 22 | GB | AE | | 87-0 | 27-51-41 | | D41630P | 5 | | | D40302J | 13 | | | 001-099 | |
| 2005B | 22 | GB | AE | | 86-0 | 27-51-41 | | D41630P | 5 | | | D40302J | 13 | | | 115-199 | |
| 2005R | 22 | GB | AE | | 0-0 | 27-51-41 | | D41630P | 6 | | | D40302J | 14 | | | ALL | |
| 4001B | 22 | GD | EA | | 87-0 | 27-51-41 | | D41630P | 1 | | | D40302J | 18 | | | 001-099 | |
| 4001B | 22 | GD | EA | | 86-0 | 27-51-41 | | D41630P | 1 | | | D40302J | 18 | | | 115-199 | |
| 4001G | 22 | GD | EA | | 0-0 | 27-51-41 | | D41630P | 2 | | | D40302J | 19 | | | ALL | |
| 4001R | 22 | GD | EA | | 0-0 | 27-51-41 | | D41630P | 3 | | | D40302J | 20 | | | ALL | |
| 4001Y | 22 | GD | EA | | 0-0 | 27-51-41 | | D41630P | 4 | | | D40302J | 21 | | | ALL | |
| 5001B | 24 | G2 | EB | | 31-0 | 28-41-11 | | D41618P | 11 | | | D41628P | 50 | | | 001-099 | |
| 5001B | 24 | G2 | EB | | 32-0 | 28-41-11 | | D41618P | 11 | | | D41628P | 50 | | | 115-199 | |
| 5001R | 24 | G2 | EB | | 0-0 | 28-41-11 | | D41618P | 12 | | | D41628P | 51 | | | ALL | |
| 5001Z | | | EB | | 0-0 | 28-41-11 | | D41618P | 13 | | | D41628P | 52 | | | ALL | |
| YAAA | | | | | 0-0 | 27-51-41 | | D40302J | S/R | | | GD03067 | ST.. | E | | 001-099 | |
| YAAA | | | | | 0-0 | 33-42-11 | | GD03067 | ST.. | E | | D40302J | S/R | | | 115-199 | |
| YAAB | | | | | 0-0 | 27-23-11 | | GD01298 | ST.. | E | | GD02534 | ST.. | E | | ALL | |
| W4206 | 286N4206 | | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A | | | | | | | | | | | | |
| 0006 | 20 | GA | | | 22-0 | 29-35-11 | | D41792P | 4 | | | SM00001 | 9 | | | 001-099 | |
| 0006 | 20 | GA | | | 21-0 | 29-35-11 | | D41792P | 4 | | | SM00001 | 9 | | | 115-199 | |
| 0007 | 20 | GA | | | 86-0 | 29-35-11 | | D41792P | 5 | | | D40964J | 6 | | | 001-099 | |
| 0007 | 20 | GA | | | 87-0 | 29-35-11 | | D41792P | 5 | | | D40964J | 6 | | | 115-199 | |
| 0010 | 20 | GA | | | 23-0 | SPARE | | D41732P | 6 | | | D41792P | 8 | | | 001-099 | |
| 0010 | 20 | GA | | | 21-0 | SPARE | | D41732P | 6 | | | D41792P | 8 | | | 115-199 | |
| 001TI | | | BE | | 0-0 | 28-41-21 | | D42220P | =C1 | | | D02792 | =C1 | | | 115-199 | |
| 001TO | | | BE | | 0-0 | 28-41-21 | | D42220P | 2 | | | GD02045 | ST.. | E | | 115-199 | |
| 001TX | 18 | TK | BE | | 72-0 | 28-41-21 | | D42220P | 1 | | | D02792 | 1 | VN | | 115-199 | |
| 0023 | 22 | GA | | | 69-0 | 27-81-21 | | D41656P | 23 | | | D41394J | 25 | | | ALL | |
| 0024 | 22 | GA | | | 69-0 | 27-81-21 | | D41656P | 24 | | | D41394J | 26 | | | ALL | |
| 002TI | | | EC | | 0-0 | 28-41-41 | | D42224P | =C1 | | | D02786 | =C1 | | | 115-199 | |
| 002TO | | | EC | | 0-0 | 28-41-41 | | D42224P | 2 | | | GD00206 | ST.. | E | | 115-199 | |
| 002TX | 18 | TK | EC | | 48-0 | 28-41-41 | | D42224P | 1 | | | D02786 | 1 | VN | | 115-199 | |
| 0034 | 20 | GA | | | 86-0 | 29-11-12 | | D41792P | 9 | | | D40964J | 12 | | | 001-099 | |
| 0034 | 20 | GA | | | 87-0 | 29-11-12 | | D41792P | 9 | | | D40964J | 12 | | | 115-199 | |
| 0035 | 20 | GA | | | 85-0 | 29-31-11 | | D41732P | 7 | | | D40964J | 7 | | | 001-099 | |
| 0035 | 20 | GA | | | 87-0 | 29-31-11 | | D41732P | 7 | | | D40964J | 7 | | | 115-199 | |
| 0038 | 22 | GA | | | 86-0 | SPARE | | D41792P | 10 | | | D40964J | 13 | | | 001-099 | |
| 0038 | 22 | GA | | | 87-0 | SPARE | | D41792P | 10 | | | D40964J | 13 | | | 115-199 | |
| 0039 | 22 | GA | | | 82-0 | SPARE | | D41792P | 11 | | | D40922P | 10 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4206 | 286N4206 | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | | | |
| 0039 | 22 | GA | | | 81-0 | SPARE | D41792P | 11 | | | D40922J | 10 | | | 115-199 |
| 0040 | 22 | GA | | | 85-0 | SPARE | D41656P | 27 | | | D40922P | 7 | | | 001-099 |
| 0040 | 22 | GA | | | 86-0 | SPARE | D41656P | 27 | | | D40922J | 7 | | | 115-199 |
| 0041 | 22 | GA | | | 69-0 | SPARE | D41656P | 28 | | | D41394J | 22 | | | ALL |
| 0042 | 20 | GA | | | 34-0 | SPARE | D41656P | 29 | | | D41636P | 10 | | | ALL |
| 0043 | 20 | GA | | | 84-0 | 29-35-11 | D40964J | 3 | | | SM00001 | | 9 | | ALL |
| 0044 | 20 | GA | | | 2-0 | 29-35-11 | D41732P | 8 | | | SM00001 | | 9 | | 001-099 |
| 0044 | 20 | GA | | | 1-0 | 29-35-11 | D41732P | 8 | | | SM00001 | | 9 | | 115-199 |
| 2001B | 20 | GB | AA | | 57-0 | 32-09-12 | D41636P | 1 | | | SP00315 | | 9 | | 001-099 |
| 2001B | 20 | GB | AA | | 60-0 | 32-09-12 | D41636P | 1 | | | SP00315 | | 9 | | 115-199 |
| 2001R | 20 | GB | AA | | 0-0 | 32-09-12 | D41636P | 2 | | | SP00313 | | 9 | | ALL |
| 2002B | 24 | GL | AB | | 58-0 | 32-61-22 | D41636P | 4 | | | SM00003 | | 9 | | 001-099 |
| 2002B | 24 | GL | AB | | 59-0 | 32-61-22 | D41636P | 4 | | | SM00003 | | 9 | | 115-199 |
| 2002R | 24 | GL | AB | | 0-0 | 32-61-22 | D41636P | 3 | | | SM00004 | | 9 | | ALL |
| 2003B | 22 | GB | AC | | 67-0 | 32-61-13 | D41636P | 6 | | | D40964J | 1 | | | 001-099 |
| 2003B | 22 | GB | AC | | 69-0 | 32-61-13 | D41636P | 6 | | | D40964J | 1 | | | 115-199 |
| 2003R | 22 | GB | AC | | 0-0 | 32-61-13 | D41636P | 5 | | | D40964J | 2 | | | ALL |
| 2004B | 22 | GB | AD | | 67-0 | 32-61-13 | D41636P | 8 | | | D40964J | 5 | | | 001-099 |
| 2004B | 22 | GB | AD | | 69-0 | 32-61-13 | D41636P | 8 | | | D40964J | 5 | | | 115-199 |
| 2004R | 22 | GB | AD | | 0-0 | 32-61-13 | D41636P | 7 | | | D40964J | 4 | | | ALL |
| 2005B | 22 | GB | AE | | 69-0 | 27-51-61 | D41656P | 3 | | | D41394J | 21 | | | ALL |
| 2005R | 22 | GB | AE | | 0-0 | 27-51-61 | D41656P | 4 | | | D41394J | 20 | | | ALL |
| 2006B | 22 | GB | AF | | 85-0 | 27-51-61 | D41656P | 5 | | | D40922P | 2 | | | 001-099 |
| 2006B | 22 | GB | AF | | 86-0 | 27-51-61 | D41656P | 5 | | | D40922J | 2 | | | 115-199 |
| 2006R | 22 | GB | AF | | 0-0 | 27-51-61 | D41656P | 6 | | | D40922P | 1 | | | 001-099 |
| 2006R | 22 | GB | AF | | 0-0 | 27-51-61 | D41656P | 6 | | | D40922J | 1 | | | 115-199 |
| 2007B | 20 | GB | AG | | 86-0 | 29-32-41 | D41792P | 7 | | | D40964J | 11 | | | 001-099 |
| 2007B | 20 | GB | AG | | 87-0 | 29-32-41 | D41792P | 7 | | | D40964J | 11 | | | 115-199 |
| 2007R | 20 | GB | AG | | 0-0 | 29-32-41 | D41792P | 6 | | | D40964J | 10 | | | ALL |
| 2008B | 20 | GB | ED | | 86-0 | 29-31-11 | D40964J | 8 | | | D41792P | 1 | | | 001-099 |
| 2008B | 20 | GB | ED | | 87-0 | 29-31-11 | D40964J | 8 | | | D41792P | 13 | | | 115-199 |
| 2008R | 20 | GB | ED | | 0-0 | 29-31-11 | D40964J | 9 | | | D41792P | 2 | | | 001-099 |
| 2008R | 20 | GB | ED | | 0-0 | 29-31-11 | D40964J | 9 | | | D41792P | 14 | | | 115-199 |
| 2502B | 20 | GF | BC | | 8-0 | 32-61-22 | D40382J | 2 | | | SM00003 | | 9 | | 115-199 |
| 2502R | 20 | GF | BC | | 0-0 | 32-61-22 | D40382J | 1 | | | SM00004 | | 9 | | 115-199 |
| 2502Z | | | BC | | 0-0 | 32-61-22 | D40382J | DED | | | SM00003 | | 9 | | 115-199 |
| 2504B | 20 | GF | BA | | 9-0 | 32-61-22 | D40382J | 2 | | | SM00003 | | 9 | | 001-099 |
| 2504R | 20 | GF | BA | | 0-0 | 32-61-22 | D40382J | 1 | | | SM00004 | | 9 | | 001-099 |
| 2504Z | | | BA | | 0-0 | 32-61-22 | D40382J | DED | | | SM00003 | | 9 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4206 | 286N4206 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | |
| 3001B | 18 | GC | CA | | 65-0 | 28-22-11 | D41732P | | 3 | | SP05006 | | 9 | | 001-099 |
| 3001B | 18 | GC | CA | | 64-0 | 28-22-11 | D41732P | | 3 | | SP05006 | | 9 | | 115-199 |
| 3001R | 18 | GC | CA | | 0-0 | 28-22-11 | D41732P | | 1 | | SP05002 | | 9 | | ALL |
| 3001Y | 18 | GC | CA | | 0-0 | 28-22-11 | D41732P | | 2 | | SP05004 | | 9 | | ALL |
| 4001B | 22 | GD | EA | | 69-0 | 27-51-61 | D41656P | | 7 | | D41394J | 17 | | | ALL |
| 4001G | 22 | GD | EA | | 0-0 | 27-51-61 | D41656P | | 8 | | D41394J | 19 | | | ALL |
| 4001R | 22 | GD | EA | | 0-0 | 27-51-61 | D41656P | | 9 | | D41394J | 16 | | | ALL |
| 4001Y | 22 | GD | EA | | 0-0 | 27-51-61 | D41656P | | 10 | | D41394J | 18 | | | ALL |
| 4002B | 22 | GD | EB | | 85-0 | 27-51-61 | D41656P | | 11 | | D40922P | 4 | | | 001-099 |
| 4002B | 22 | GD | EB | | 85-0 | 27-51-61 | D41656P | | 11 | | D40922J | 4 | | | 115-199 |
| 4002G | 22 | GD | EB | | 0-0 | 27-51-61 | D41656P | | 12 | | D40922P | 6 | | | 001-099 |
| 4002G | 22 | GD | EB | | 0-0 | 27-51-61 | D41656P | | 12 | | D40922J | 6 | | | 115-199 |
| 4002R | 22 | GD | EB | | 0-0 | 27-51-61 | D41656P | | 13 | | D40922P | 3 | | | 001-099 |
| 4002R | 22 | GD | EB | | 0-0 | 27-51-61 | D41656P | | 13 | | D40922J | 3 | | | 115-199 |
| 4002Y | 22 | GD | EB | | 0-0 | 27-51-61 | D41656P | | 14 | | D40922P | 5 | | | 001-099 |
| 4002Y | 22 | GD | EB | | 0-0 | 27-51-61 | D41656P | | 14 | | D40922J | 5 | | | 115-199 |
| 4501AA | 20 | 4K | BA | | 48-0 | SPARE | D41636P | | 23 | | D41394J | 14 | | | 115-199 |
| 4501RB | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 15 | | D41394J | 5 | | | 115-199 |
| 4501RG | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 14 | | D41394J | 4 | | | 115-199 |
| 4501RK | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 13 | | D41394J | 3 | | | 115-199 |
| 4501RV | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 17 | | D41394J | 7 | | | 115-199 |
| 4501RY | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 12 | | D41394J | 2 | | | 115-199 |
| 4501W | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 11 | | D41394J | 1 | | | 115-199 |
| 4501WB | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 25 | | D41394J | 13 | | | 115-199 |
| 4501WG | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 22 | | D41394J | 12 | | | 115-199 |
| 4501WK | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 16 | | D41394J | 6 | | | 115-199 |
| 4501WN | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 18 | | D41394J | 8 | | | 115-199 |
| 4501WO | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 21 | | D41394J | 11 | | | 115-199 |
| 4501WR | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 19 | | D41394J | 9 | | | 115-199 |
| 4501WV | 20 | 4K | BA | | 0-0 | SPARE | D41636P | | 24 | | D41394J | 15 | | | 115-199 |
| 4501WY | 20 | 4K | BA | | 0-0 | 28-41-21 | D41636P | | 20 | | D41394J | 10 | | | 115-199 |
| 4501Z | | | BA | | 0-0 | 28-41-21 | D41636P | | 9 | | D41394J | S/R | | | 115-199 |
| 4502B | 20 | 4L | BB | | 51-0 | 28-41-41 | D41636P | | 26 | | D02784 | 1 | | | 115-199 |
| 4502G | 20 | 4L | BB | | 0-0 | 28-41-41 | D41636P | | 28 | | D02784 | 3 | | | 115-199 |
| 4502K | 20 | 4L | BB | | 0-0 | 28-41-41 | D41636P | | 30 | | D02784 | 5 | | | 115-199 |
| 4502R | 20 | 4L | BB | | 0-0 | 28-41-41 | D41636P | | 27 | | D02784 | 2 | | | 115-199 |
| 4502Y | 20 | 4L | BB | | 0-0 | 28-41-41 | D41636P | | 29 | | D02784 | 4 | | | 115-199 |
| 4502Z | | | BB | | 0-0 | 28-41-41 | D41636P | | 31 | | GD00211 | ST.. | E | | 115-199 |
| FRZA | | | | | 0-6 | 28-41-41 | D02784 | | | ZA | GD00211 | ST.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | Effectivity |
|--------------|-----------------|--|------------------------|------------------------|-------------|
| Wire No. | GA CO TY Fam | FT-IN Diagram | Equip Term Type Splice | Equip Term Type Splice | |
| W4206 | 286N4206 | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | |
| FRZD | | 0-6 28-41-41 | D02786 | | 115-199 |
| YAAA | | 0-0 28-41-41 | GD03073 | ST.. E * | 115-199 |
| YAAC | | 0-0 SPARE | D41394J | S/R | 001-099 |
| YAAC | | 0-0 27-51-61 | GD02550 | ST.. E * | 115-199 |
| YAAD | | 0-0 28-41-41 | GD03073 | ST.. E * | 115-199 |
| YAAE | | 0-0 28-41-21 | GD03073 | ST.. E * | 115-199 |
| YAAF | | 0-0 32-61-12 | GD02550 | ST.. E * | 115-199 |
| YAAH | | 0-0 27-51-61 | GD03073 | ST.. E * | 115-199 |
| YAAI | | 0-0 27-51-61 | D40922P | S/R | 001-099 |
| YAAJ | | 0-0 32-61-22 | D40382J | S/R | 001-099 |
| | | | | | |
| W4208 | 286N4208 | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - R1B | | | |
| 0001 | 24 | GK | 29-0 27-81-11 | D41694P 1 | 001-099 |
| 0001 | 22 | GA | 29-0 27-81-11 | D41694P 1 | 115-199 |
| 0002 | 24 | GK | 29-0 27-81-11 | D41694P 2 | 001-099 |
| 0002 | 22 | GA | 29-0 27-81-11 | D41694P 2 | 115-199 |
| 0003 | 14 | GA | 74-0 27-81-11 | D41692P 14 | 001-099 |
| 0003 | 14 | GA | 73-0 27-81-11 | D41692P 14 | 115-199 |
| 0005 | 14 | GA | 74-0 27-81-11 | D41692P 16 | 001-099 |
| 0005 | 14 | GA | 73-0 27-81-11 | D41692P 16 | 115-199 |
| 0006 | 14 | GA | 74-0 27-81-11 | D41692P 18 | 001-099 |
| 0006 | 14 | GA | 73-0 27-81-11 | D41692P 18 | 115-199 |
| 0007 | 22 | GA | 68-0 27-81-21 | D41696P 1 | ALL |
| 0008 | 22 | GA | 68-0 27-81-21 | D41696P 2 | ALL |
| 0009 | 24 | GK | 29-0 27-51-11 | D41694P 3 | 001-099 |
| 0009 | 22 | GA | 29-0 27-51-11 | D41694P 3 | 115-199 |
| 0010 | 24 | GK | 29-0 27-51-11 | D41694P 4 | 001-099 |
| 0010 | 22 | GA | 29-0 27-51-11 | D41694P 4 | 115-199 |
| 0011 | 14 | GA | 92-0 27-51-11 | D41692P 20 | ALL |
| 0012 | 14 | GA | 92-0 27-51-11 | D41692P 22 | ALL |
| 0013 | 14 | GA | 92-0 27-51-11 | D41692P 24 | ALL |
| 0014 | 22 | GA | 92-0 27-51-21 | D41692P 17 | 001-099 |
| 0014 | 22 | GA | 90-0 27-51-21 | D41692P 17 | 115-199 |
| 0015 | 22 | GA | 74-0 27-51-21 | D41692P 19 | 001-099 |
| 0015 | 22 | GA | 71-0 27-51-21 | D41692P 19 | 115-199 |
| 0016 | 22 | GA | 24-0 27-51-21 | D41694P 17 | ALL |
| 0017 | 22 | GA | 92-0 27-51-21 | D41692P 6 | 001-099 |
| 0017 | 22 | GA | 90-0 27-51-21 | D41692P 6 | 115-199 |
| 0018 | 22 | GA | 92-0 27-51-21 | D41692P 7 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4208 | 286N4208 | | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - R1B (continued) | | | | | | | | | | | | |
| 0018 | 22 | | GA | | 90-0 | 27-51-21 | D41692P | | 7 | | D40342J | | 9 | | 115-199 | | |
| 0019 | 22 | | GA | | 92-0 | 27-51-21 | D41692P | | 8 | | D40342J | | 25 | | 001-099 | | |
| 0019 | 22 | | GA | | 90-0 | 27-51-21 | D41692P | | 8 | | D40342J | | 25 | | 115-199 | | |
| 0020 | 22 | | GA | | 76-0 | 27-51-21 | D41692P | | 9 | | D01710 | | 2 | | 001-099 | | |
| 0020 | 20 | | GA | | 75-0 | 27-51-21 | D41692P | | 9 | | D01710 | | 2 | | 115-199 | | |
| 0021 | 22 | | GA | | 9-0 | 27-51-21 | D41692P | | 10 | | SM00001 | | | 9 | ALL | | |
| 0022 | 22 | | GA | | 29-0 | 27-51-21 | D41692P | | 11 | | D41696P | | 6 | | ALL | | |
| 0023 | 20 | | GA | | 86-0 | 22-11-22 | D41624P | | 21 | | D40342J | | 14 | | ALL | | |
| 0024 | 20 | | GA | | 86-0 | 22-11-22 | D41624P | | 2 | | D40342J | | 18 | | ALL | | |
| 0025 | 22 | | GA | | 69-0 | 27-51-21 | D01710 | | 3 | | SM00001 | | | 9 | 001-099 | | |
| 0025 | 20 | | GA | | 69-0 | 27-51-21 | D01710 | | 3 | | SM00001 | | | 9 | 115-199 | | |
| 0026 | 20 | | GA | | 8-0 | 21-31-21 | D41694P | | 9 | | D41696P | | 7 | | 001-099 | | |
| 0026 | 20 | | GA | | 9-0 | 21-31-21 | D41694P | | 9 | | D41696P | | 7 | | 115-199 | | |
| 0027 | 24 | | GK | | 8-0 | 21-31-21 | D41694P | | 26 | | D41696P | | 8 | | 001-099 | | |
| 0027 | 24 | | GK | | 9-0 | 21-31-21 | D41694P | | 26 | | D41696P | | 8 | | 115-199 | | |
| 0028 | 24 | | GK | | 8-0 | 21-31-21 | D41694P | | 29 | | D41696P | | 9 | | 001-099 | | |
| 0028 | 24 | | GK | | 9-0 | 21-31-21 | D41694P | | 29 | | D41696P | | 9 | | 115-199 | | |
| 0029 | 22 | | GA | | 74-0 | 27-51-21 | D41692P | | 15 | | D40076J | | 1 | | 001-099 | | |
| 0029 | 20 | | GA | | 71-0 | 27-51-21 | D41692P | | 15 | | D40076J | | 1 | | 115-199 | | |
| 0030 | 20 | | GA | | 66-0 | SPARE | D41766P | | 1 | | D40076J | | 11 | | ALL | | |
| 0031 | 20 | | GA | | 66-0 | SPARE | D41766P | | 2 | | D40076J | | 16 | | ALL | | |
| 0035 | 22 | | GA | | 11-0 | 27-62-11 | D41766P | | 6 | | D41624P | | 13 | | 001-099 | | |
| 0035 | 20 | | GA | | 11-0 | 27-62-11 | D41766P | | 6 | | D41624P | | 13 | | 115-199 | | |
| 0036 | 22 | | GA | | 11-0 | 27-62-11 | D41766P | | 7 | | D41624P | | 14 | | 001-099 | | |
| 0036 | 20 | | GA | | 11-0 | 27-62-11 | D41766P | | 7 | | D41624P | | 14 | | 115-199 | | |
| 0037 | 22 | | GA | | 92-0 | SPARE | D40342J | | 6 | | D41692P | | 3 | | 001-099 | | |
| 0037 | 22 | | GA | | 86-0 | SPARE | D40342J | | 6 | | D41766P | | 8 | | 115-199 | | |
| 0038 | 22 | | GA | | 87-0 | SPARE | D40342J | | 20 | | D41694P | | 16 | | ALL | | |
| 0039 | 22 | | GA | | 76-0 | 27-51-21 | D01710 | | 5 | | D41692P | | 21 | | 001-099 | | |
| 0039 | 20 | | GA | | 75-0 | 27-51-21 | D01710 | | 5 | | D41692P | | 21 | | 115-199 | | |
| 0040 | 18 | | GA | | 2-0 | 27-51-21 | D01710 | | 1 | | GD02499 | DC.. | | E | 001-099 | | |
| 0040 | 18 | | GA | | 3-0 | 27-51-21 | D01710 | | 1 | | GD02499 | DC.. | | E | 115-199 | | |
| 0041 | 22 | | GA | | 29-0 | SPARE | D41692P | | 12 | | D41694P | | 33 | | ALL | | |
| 0042 | 22 | | GA | | 29-0 | SPARE | D41692P | | 13 | | D41694P | | 34 | | ALL | | |
| 0043 | 20 | | GA | | 67-0 | SPARE | D41694P | | 21 | | D40076J | | 10 | | 001-099 | | |
| 0043 | 20 | | GA | | 86-0 | SPARE | D41696P | | 22 | | D40342J | | 22 | | 115-199 | | |
| 0044 | 22 | | GA | | 29-0 | 27-51-21 | D41696P | | 4 | | D41692P | | 23 | | ALL | | |
| 0045 | 22 | | GA | | 29-0 | 27-51-21 | D41696P | | 5 | | D41692P | | 25 | | ALL | | |
| 2001B | 22 | | GB | AA | 67-0 | 27-81-11 | D41694P | | 5 | | D40076J | | 3 | | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4208 | 286N4208 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - R1B (continued) | | | | | | | | | | | |
| 2001R | 22 | GB | AA | | 0-0 | 27-81-11 | D41694P | 6 | | | D40076J | 2 | | | ALL |
| 2002B | 22 | GB | AB | | 87-0 | 27-51-11 | D41694P | 7 | | | D40342J | 28 | | | 001-099 |
| 2002B | 22 | GB | AB | | 86-0 | 27-51-11 | D41694P | 7 | | | D40342J | 28 | | | 115-199 |
| 2002R | 22 | GB | AB | | 0-0 | 27-51-11 | D41694P | 8 | | | D40342J | 27 | | | ALL |
| 2003B | 20 | GB | AC | | 86-0 | 22-11-21 | D41624P | 3 | | | D40342J | 4 | | | ALL |
| 2003R | 20 | GB | AC | | 0-0 | 22-11-21 | D41624P | 4 | | | D40342J | 24 | | | ALL |
| 2004B | 20 | GB | AD | | 86-0 | 22-13-21 | D41624P | 5 | | | D40342J | 8 | | | ALL |
| 2004R | 20 | GB | AD | | 0-0 | 22-13-21 | D41624P | 6 | | | D40342J | 7 | | | ALL |
| 3001B | 20 | GC | CA | | 86-0 | 22-13-21 | D41624P | 7 | | | D40342J | 17 | | | ALL |
| 3001R | 20 | GC | CA | | 0-0 | 22-13-21 | D41624P | 8 | | | D40342J | 21 | | | ALL |
| 3001Y | 20 | GC | CA | | 0-0 | 22-13-21 | D41624P | 9 | | | D40342J | 16 | | | ALL |
| 3002B | 20 | GC | CB | | 86-0 | 22-13-21 | D41624P | 10 | | | D40342J | 12 | | | ALL |
| 3002R | 20 | GC | CB | | 0-0 | 22-13-21 | D41624P | 11 | | | D40342J | 11 | | | ALL |
| 3002Y | 20 | GC | CB | | 0-0 | 22-13-21 | D41624P | 12 | | | D40342J | 13 | | | ALL |
| 4001B | 22 | GD | EA | | 67-0 | 27-81-11 | D41694P | 24 | | | D40076J | 5 | | | ALL |
| 4001G | 22 | GD | EA | | 0-0 | 27-81-11 | D41694P | 10 | | | D40076J | 12 | | | ALL |
| 4001R | 22 | GD | EA | | 0-0 | 27-81-11 | D41694P | 11 | | | D40076J | 4 | | | ALL |
| 4001Y | 22 | GD | EA | | 0-0 | 27-81-11 | D41694P | 25 | | | D40076J | 6 | | | ALL |
| 4002B | 22 | GD | EB | | 87-0 | 27-51-11 | D41694P | 27 | | | D40342J | 2 | | | ALL |
| 4002G | 22 | GD | EB | | 0-0 | 27-51-11 | D41694P | 12 | | | D40342J | 5 | | | ALL |
| 4002R | 22 | GD | EB | | 0-0 | 27-51-11 | D41694P | 13 | | | D40342J | 1 | | | ALL |
| 4002Y | 22 | GD | EB | | 0-0 | 27-51-11 | D41694P | 28 | | | D40342J | 3 | | | ALL |
| 4251B | 22 | GW | GA | | 7-0 | 21-31-21 | D41694P | 14 | | | D41696P | 12 | | | 001-099 |
| 4251B | 22 | GW | GA | | 10-0 | 21-31-21 | D41694P | 14 | | | D41696P | 12 | | | 115-199 |
| 4251G | 22 | GW | GA | | 0-0 | 21-31-21 | D41694P | 15 | | | D41696P | 25 | | | ALL |
| 4251R | 22 | GW | GA | | 0-0 | 21-31-21 | D41694P | 31 | | | D41696P | 13 | | | ALL |
| 4251Y | 22 | GW | GA | | 0-0 | 21-31-21 | D41694P | 30 | | | D41696P | 11 | | | ALL |
| 4251Z | | | GA | | 0-0 | 21-31-21 | D41694P | 32 | | | D41696P | 24 | | | ALL |
| YAAA | | | | | 0-0 | 27-51-21 | D40076J | S/R | | | GD03075 | ST.. | E | * | 001-099 |
| YAAB | | | | | 0-0 | 27-51-21 | GD02497 | ST.. | E | | GD03075 | ST.. | E | * | 001-099 |
| YAAB | | | | | 0-0 | 27-81-11 | GD03075 | ST.. | E | * | D40076J | S/R | | | 115-199 |
| YAAC | | | | | 0-0 | 27-51-21 | GD03075 | ST.. | E | * | GD02497 | ST.. | E | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4200

Page 15 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC | | | | | | | | | | | |
| 0001 | 22 | | GA | | 64-0 | SPARE | D40006J | 40 | | | D41958P | 38 | | | 115-199 |
| 0002 | 22 | | GA | | 64-0 | SPARE | D40006J | 41 | | | D41958P | 39 | | | 115-199 |
| 0004 | 22 | | GA | | 67-0 | 30-21-11 | D41734P | 6 | | | D40006J | 12 | | | 001-099 |
| 0004 | 22 | | GA | | 67-0 | 30-21-11 | D40006J | 11 | | | D41734P | 1 | | | 115-199 |
| 0005 | 22 | | GA | | 67-0 | 30-21-11 | D41734P | 5 | | | D40006J | 11 | | | 001-099 |
| 0005 | 22 | | GA | | 67-0 | 30-21-11 | D40006J | 12 | | | D41734P | 6 | | | 115-199 |
| 0006 | 22 | | GA | | 66-0 | 30-21-11 | D41958P | 22 | | | D40006J | 13 | | | 001-099 |
| 0006 | 22 | | GA | | 64-0 | 30-21-11 | D40006J | 13 | | | D41958P | 2 | | | 115-199 |
| 0007 | 22 | | GA | | 66-0 | 76-11-11 | D41958P | 4 | | | D40006J | 37 | | | 001-099 |
| 0007 | 22 | | GA | | 64-0 | 76-11-11 | D40006J | 37 | | | D41958P | 4 | | | 115-199 |
| 0008 | 22 | | GA | | 66-0 | 76-11-11 | D41958P | 3 | | | D40006J | 36 | | | 001-099 |
| 0008 | 22 | | GA | | 64-0 | 76-11-11 | D40006J | 36 | | | D41958P | 3 | | | 115-199 |
| 0009 | 20 | | GA | | 57-0 | 74-31-11 | SM00003 | | 9 | | D40006J | 17 | | | 001-099 |
| 0009 | 20 | | GA | | 64-0 | 74-31-11 | D40006J | 17 | | | D41958P | 5 | | | 115-199 |
| 0010 | 20 | | GA | | 66-0 | 74-31-11 | D40006J | 18 | | | D41958P | 6 | | | 001-099 |
| 0010 | 20 | | GA | | 64-0 | 74-31-11 | D40006J | 18 | | | D41958P | 6 | | | 115-199 |
| 0012 | 22 | | GA | | 66-0 | 78-36-11 | D40006J | 34 | | | D41958P | 8 | | | 001-099 |
| 0012 | 22 | | GA | | 64-0 | 78-36-11 | D40006J | 34 | | | D41958P | 8 | | | 115-199 |
| 0013 | 22 | | GA | | 66-0 | 78-36-11 | D40006J | 35 | | | D41958P | 9 | | | 001-099 |
| 0013 | 22 | | GA | | 64-0 | 78-36-11 | D40006J | 35 | | | D41958P | 9 | | | 115-199 |
| 0014 | 22 | | GA | | 69-0 | 26-18-11 | D40006J | 8 | | | D42000P | 1 | | | 001-099 |
| 0014 | 20 | | GA | | 68-0 | 26-18-11 | D40006J | 8 | | | D42000P | 1 | | | 115-199 |
| 0015 | 22 | | GA | | 69-0 | 26-18-11 | D40006J | 9 | | | D42000P | 2 | | | 001-099 |
| 0015 | 20 | | GA | | 68-0 | 26-18-11 | D40006J | 9 | | | D42000P | 2 | | | 115-199 |
| 0016 | 22 | | GA | | 23-0 | 26-11-12 | D41986P | 1 | | | D41734P | 17 | | | 001-099 |
| 0016 | 22 | | GA | | 24-0 | 26-11-12 | D41986P | 1 | | | D41734P | 17 | | | 115-199 |
| 0017 | 22 | | GA | | 23-0 | SPARE | D41986P | 2 | | | D41734P | 18 | | | 001-099 |
| 0017 | 22 | | GA | | 24-0 | 26-11-12 | D41986P | 2 | | | D41734P | 18 | | | 115-199 |
| 0018 | 22 | | GA | | 69-0 | 26-11-12 | D41986P | 10 | | | D40042J | 6 | | | 001-099 |
| 0018 | 20 | | GA | | 68-0 | 26-11-12 | D41986P | 10 | | | D40042J | 6 | | | 115-199 |
| 0019 | 22 | | GA | | 69-0 | 26-11-12 | D41986P | 4 | | | D40042J | 2 | | | 001-099 |
| 0019 | 20 | | GA | | 68-0 | 26-11-12 | D41986P | 4 | | | D40042J | 2 | | | 115-199 |
| 0020 | 20 | | GA | | 69-0 | 26-12-11 | D41986P | 5 | | | D40042J | 3 | | | 001-099 |
| 0020 | 20 | | GA | | 68-0 | 26-12-11 | D41986P | 5 | | | D40042J | 3 | | | 115-199 |
| 0021 | 20 | | GA | | 69-0 | 26-12-11 | D41986P | 6 | | | D40042J | 4 | | | 001-099 |
| 0021 | 20 | | GA | | 68-0 | 26-12-11 | D41986P | 6 | | | D40042J | 4 | | | 115-199 |
| 0022 | 22 | | GA | | 23-0 | 26-12-11 | D41986P | 7 | | | D41734P | 19 | | | 001-099 |
| 0022 | 22 | | GA | | 24-0 | 26-12-11 | D41986P | 7 | | | D41734P | 19 | | | 115-199 |
| 0023 | 20 | | GA | | 104-0 | 28-25-21 | D40350J | 22 | | | TB0158X | A003 | BJ | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0024 | 24 | | GK | | 32-0 | 78-36-11 | D42016P | 11 | | | D41958P | 27 | | | 001-099 |
| 0024 | 24 | | GK | | 29-0 | 78-36-11 | D42016P | 11 | | | D41958P | 42 | | | 115-199 |
| 0025 | 24 | | GK | | 30-0 | 78-36-11 | D42016P | 12 | | | D41734P | 22 | | | 001-099 |
| 0025 | 24 | | GK | | 29-0 | 78-36-11 | D42016P | 12 | | | D41734P | 22 | | | 115-199 |
| 0026 | 24 | | GK | | 15-0 | 78-36-11 | D41958P | 10 | | | D41734P | 25 | | | 001-099 |
| 0026 | 24 | | GK | | 12-0 | 78-36-11 | D41734P | 25 | | | D41958P | 10 | | | 115-199 |
| 0027 | 20 | | GA | | 64-0 | 29-33-11 | D40350J | 20 | | | D42016P | 45 | | | 001-099 |
| 0027 | 20 | | GA | | 137-0 | 29-33-11 | D40350J | 20 | | | D41686P | 1 | | | 115-199 |
| 0028 | 20 | | GA | | 7-0 | 33-13-31 | D03572 | 1 | | | TB0114Z | 8 | BJ | | ALL |
| 0029 | 20 | | GA | | 7-0 | 33-13-31 | D03572 | 2 | | | TB0114Z | 10 | BJ | | ALL |
| 0031 | 20 | | GA | | 64-0 | 29-33-11 | D40350J | 25 | | | D42016P | 44 | | | 001-099 |
| 0031 | 20 | | GA | | 137-0 | 29-33-11 | D40350J | 25 | | | D41686P | 5 | | | 115-199 |
| 0032 | 20 | | GA | | 64-0 | 29-33-11 | D40350J | 26 | | | D42016P | 46 | | | 001-099 |
| 0032 | 20 | | GA | | 137-0 | 29-33-11 | D40350J | 26 | | | D41686P | 6 | | | 115-199 |
| 0033 | 22 | | GA | | 86-0 | 26-17-11 | D41406J | 6 | | | D42000P | 3 | | | 001-099 |
| 0033 | 20 | | GA | | 86-0 | 26-17-11 | D41406J | 6 | | | D42000P | 3 | | | 115-199 |
| 0034 | 22 | | GA | | 23-0 | 26-17-11 | D41734P | 26 | | | D42000P | 4 | | | 001-099 |
| 0034 | 22 | | GA | | 24-0 | 26-17-11 | D41734P | 26 | | | D42000P | 4 | | | 115-199 |
| 0035 | 22 | | GA | | 23-0 | 26-17-11 | D41734P | 27 | | | D42000P | 5 | | | 001-099 |
| 0035 | 22 | | GA | | 24-0 | 26-17-11 | D41734P | 27 | | | D42000P | 5 | | | 115-199 |
| 0039 | 22 | | GA | | 23-0 | 26-15-11 | D41734P | 28 | | | D41986P | 13 | | | 001-099 |
| 0039 | 22 | | GA | | 24-0 | 26-15-11 | D41734P | 28 | | | D41986P | 13 | | | 115-199 |
| 0040 | 20 | | GA | | 83-0 | 28-22-31 | D41958P | 17 | | | D41406J | 4 | | | 001-099 |
| 0040 | 20 | | GA | | 82-0 | 28-22-31 | D41958P | 17 | | | D41406J | 4 | | | 115-199 |
| 0041 | 20 | | GA | | 83-0 | 28-22-31 | D41958P | 18 | | | D41406J | 3 | | | 001-099 |
| 0041 | 20 | | GA | | 82-0 | 28-22-31 | D41958P | 18 | | | D41406J | 3 | | | 115-199 |
| 0042 | 20 | | GA | | 83-0 | 28-22-31 | D41958P | 19 | | | D41406J | 2 | | | 001-099 |
| 0042 | 20 | | GA | | 82-0 | 28-22-31 | D41958P | 19 | | | D41406J | 2 | | | 115-199 |
| 0043 | 22 | | GA | | 23-0 | 26-18-11 | D41734P | 29 | | | D42000P | 6 | | | 001-099 |
| 0043 | 22 | | GA | | 24-0 | 26-18-11 | D41734P | 29 | | | D42000P | 6 | | | 115-199 |
| 0044 | 22 | | GA | | 69-0 | 26-18-11 | D40478J | 1 | | | D42000P | 7 | | | 001-099 |
| 0044 | 20 | | GA | | 68-0 | 26-18-11 | D40478J | 1 | | | D42000P | 7 | | | 115-199 |
| 0045 | 22 | | GA | | 69-0 | 26-18-11 | D40478J | 2 | | | D42000P | 8 | | | 001-099 |
| 0045 | 20 | | GA | | 68-0 | 26-18-11 | D40478J | 2 | | | D42000P | 8 | | | 115-199 |
| 0046 | 22 | | GA | | 69-0 | 26-18-11 | D40478J | 3 | | | D42000P | 9 | | | 001-099 |
| 0046 | 20 | | GA | | 68-0 | 26-18-11 | D40478J | 3 | | | D42000P | 9 | | | 115-199 |
| 0047 | 22 | | GA | | 69-0 | 26-18-11 | D40478J | 4 | | | D42000P | 10 | | | 001-099 |
| 0047 | 20 | | GA | | 68-0 | 26-18-11 | D40478J | 4 | | | D42000P | 10 | | | 115-199 |
| 0048 | 22 | | GA | | 30-0 | 31-51-21 | D41986P | 12 | | | D42016P | 13 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0049 | 24 | | GK | | 30-0 | 29-33-11 | | D42016P | | | | D41734P | | | | 001-099 |
| 0049 | 22 | | GA | | 157-0 | 29-33-11 | | D41734P | | | | D41686P | | | | 115-199 |
| 0050 | 24 | | GK | | 30-0 | 29-33-11 | | D42016P | | | | D41734P | | | | 001-099 |
| 0050 | 22 | | GA | | 157-0 | 29-33-11 | | D41734P | | | | D41686P | | | | 115-199 |
| 0051 | 24 | | GK | | 30-0 | 29-33-11 | | D42016P | | | | D41734P | | | | 001-099 |
| 0051 | 22 | | GA | | 157-0 | 29-33-11 | | D41734P | | | | D41686P | | | | 115-199 |
| 0054 | 22 | | GA | | 157-0 | SPARE | | D41734P | | | | D41686P | | | | 115-199 |
| 0055 | 22 | | GA | | 157-0 | SPARE | | D41734P | | | | D41686P | | | | 115-199 |
| 0056 | 22 | | GA | | 68-0 | 29-32-11 | | D41734P | | | | D40006J | | | | 001-099 |
| 0056 | 22 | | GA | | 67-0 | 29-32-11 | | D40006J | | | | D41734P | | | | 115-199 |
| 0057 | 24 | | GK | | 30-0 | 31-51-33 | | D41986P | | | | D42016P | | | | ALL |
| 0058 | 20 | | GA | | 39-0 | 74-31-11 | | D03572 | | | | D41958P | | | | 115-199 |
| 0059 | 20 | | GA | | 39-0 | 74-31-11 | | D03572 | | | | D41958P | | | | 115-199 |
| 0061 | 20 | | GA | | 4-0 | 74-31-11 | | D03572 | | | | GD00604 | DC.. | 2 | | 001-099 |
| 0061 | 20 | | GA | | 5-0 | 74-31-11 | | D03572 | | | | GD00604 | DC.. | 2 | | 115-199 |
| 0062 | 20 | | GA | | 9-0 | 74-31-11 | | D03572 | | | | TB0116X | D011 | BJ | | ALL |
| 0063 | 20 | | GA | | 41-0 | 74-31-11 | | D41958P | | | | D03572 | | | | 001-099 |
| 0064 | 20 | | GA | | 41-0 | 74-31-11 | | D41958P | | | | D03572 | | | | 001-099 |
| 0065 | 20 | | GA | | 41-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 001-099 |
| 0065 | 20 | | GA | | 39-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 115-199 |
| 0066 | 20 | | GA | | 41-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 001-099 |
| 0066 | 20 | | GA | | 39-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 115-199 |
| 0067 | 20 | | GA | | 41-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 001-099 |
| 0067 | 20 | | GA | | 39-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 115-199 |
| 0068 | 20 | | GA | | 41-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 001-099 |
| 0068 | 20 | | GA | | 5-0 | 80-11-11 | | D03572 | | | | GD00604 | DC.. | 2 | | 115-199 |
| 0069 | 24 | | GK | | 41-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 001-099 |
| 0069 | 24 | | GK | | 39-0 | 80-11-11 | | D03572 | | | | D41958P | | | | 115-199 |
| 0070 | 22 | | GA | | 15-0 | 30-21-11 | | D41734P | | | | D41958P | | | | 001-099 |
| 0070 | 22 | | GA | | 12-0 | 30-21-11 | | D41734P | | | | D41958P | | | | 115-199 |
| 0071 | 22 | | GA | | 15-0 | 30-21-11 | | D41734P | | | | D41958P | | | | 001-099 |
| 0071 | 22 | | GA | | 12-0 | 30-21-11 | | D41734P | | | | D41958P | | | | 115-199 |
| 0072 | 22 | | GA | | 23-0 | 30-21-11 | | D41734P | | | | D42000P | | | | 001-099 |
| 0072 | 22 | | GA | | 24-0 | 30-21-11 | | D41734P | | | | D42000P | | | | 115-199 |
| 0074 | 24 | | GK | | 27-0 | 78-36-11 | | D41958P | | | | D42016P | | | | 001-099 |
| 0074 | 24 | | GK | | 26-0 | 78-36-11 | | D41958P | | | | D42016P | | | | 115-199 |
| 0075 | 20 | | GA | | 83-0 | 28-22-31 | | D41406J | | | | D41958P | | | | 001-008 |
| 0075 | 20 | | GA | | 82-0 | 28-22-31 | | D41406J | | | | D41958P | | | | 115-199 |
| 0076 | 22 | | GA | | 9-0 | 33-16-52 | | D03572 | | | | TB0116Z | | 3 | BJ | ALL |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0077 | 22 | GA | | | 9-0 | 33-16-62 | D03572 | | 3 | | TB0116Z | 4 | BJ | | ALL |
| 0078 | 22 | GA | | | 22-0 | 26-15-11 | D41986P | | 15 | | D41958P | 24 | | | 001-099 |
| 0078 | 22 | GA | | | 21-0 | 26-15-11 | D41986P | | 15 | | D41958P | 24 | | | 115-199 |
| 0079 | 22 | GA | | | 21-0 | 26-15-11 | D41986P | | 16 | | D41958P | 25 | | | 115-199 |
| 0080 | 22 | GA | | | 22-0 | 26-15-11 | D41986P | | 17 | | D41958P | 26 | | | 001-099 |
| 0080 | 22 | GA | | | 21-0 | 26-15-11 | D41986P | | 17 | | D41958P | 26 | | | 115-199 |
| 0081 | 22 | GA | | | 23-0 | 26-16-11 | D41986P | | 18 | | D41734P | 40 | | | 001-099 |
| 0081 | 22 | GA | | | 24-0 | 26-16-11 | D41986P | | 18 | | D41734P | 40 | | | 115-199 |
| 0082 | 22 | GA | | | 27-0 | SPARE | D42016P | | 27 | | D41958P | CAP | Y | | 001-099 |
| 0082 | 22 | GA | | | 21-0 | 26-15-11 | D41986P | | 19 | | D41958P | 27 | | | 115-199 |
| 0083 | 22 | GA | | | 21-0 | 26-15-11 | D41986P | | 20 | | D41958P | 28 | | | 115-199 |
| 0084 | 20 | GA | | | 69-0 | SPARE | D40042J | | 5 | | D41986P | 3 | | | 001-099 |
| 0084 | 22 | GA | | | 21-0 | SPARE | D41986P | | 21 | | D41958P | CAP | Y | | 115-199 |
| 0085 | 22 | GA | | | 21-0 | SPARE | D41986P | | 22 | | D41958P | CAP | Y | | 115-199 |
| 0088 | 20 | GA | | | 27-0 | 32-35-11 | D41958P | | 32 | | D42016P | 17 | | | 001-099 |
| 0088 | 20 | GA | | | 26-0 | 32-35-11 | D41958P | | 32 | | D42016P | 17 | | | 115-199 |
| 0089 | 22 | GA | | | 27-0 | 32-61-21 | D41958P | | 33 | | D42016P | 18 | | | 001-099 |
| 0089 | 22 | GA | | | 26-0 | 32-61-21 | D41958P | | 33 | | D42016P | 18 | | | 115-199 |
| 0090 | 18 | GA | | | 9-0 | 73-21-11 | D03572 | | 26 | 18 | TB0116F | A008 | 2 | | 001-099 |
| 0090 | 18 | GA | | | 27-0 | 73-21-11 | D03572 | | 26 | 18 | TB0158F | A011 | 2 | | 115-199 |
| 0091 | 18 | GA | | | 9-0 | 73-21-11 | D03572 | | 10 | 18 | TB0116F | C008 | 2 | | 001-099 |
| 0091 | 18 | GA | | | 27-0 | 73-21-11 | D03572 | | 10 | 18 | TB0158F | C011 | 2 | | 115-199 |
| 0092 | 20 | GA | | | 4-0 | 73-21-11 | D03572 | | 23 | | GD00604 | DC.. | 2 | | 001-099 |
| 0092 | 20 | GA | | | 5-0 | 73-21-11 | D03572 | | 23 | | GD00604 | DC.. | 2 | | 115-199 |
| 0093 | 24 | GK | | | 29-0 | 73-21-11 | D03572 | | 24 | | TB0158X | B004 | BJ | | 001-099 |
| 0093 | 24 | GK | | | 27-0 | 73-21-11 | D03572 | | 24 | | TB0158X | B004 | BJ | | 115-199 |
| 0094 | 24 | GK | | | 44-0 | 73-21-11 | D41734P | | 42 | | SM00001 | | 9 | | 001-099 |
| 0094 | 24 | GK | | | 43-0 | 73-21-11 | SM00001 | | | 9 | D41734P | 42 | | | 115-199 |
| 0095 | 22 | GA | | | 25-0 | 26-11-11 | TB0100X | A001 | BJ | | D41986P | 23 | | | 115-199 |
| 0096 | 22 | GA | | | 86-0 | 29-22-11 | D40350J | | 14 | | D42000P | 16 | | | ALL |
| 0097 | 22 | GA | | | 64-0 | 29-22-11 | D40350J | | 13 | | D42016P | 28 | | | ALL |
| 0098 | 22 | GA | | | 86-0 | 29-22-11 | D40350J | | 16 | | D42000P | 18 | | | ALL |
| 0100 | 22 | GA | | | 157-0 | SPARE | D41734P | | 45 | | D41686P | 15 | | | 115-199 |
| 0102 | 24 | GK | | | 27-0 | 29-33-11 | D41958P | | 41 | | D42016P | 53 | | | 001-099 |
| 0102 | 24 | GK | | | 154-0 | 29-33-11 | D41958P | | 41 | | D41686P | 17 | | | 115-199 |
| 0103 | 22 | GA | | | 68-0 | SPARE | D41734P | | 47 | | D40006J | 40 | | | 001-099 |
| 0103 | 22 | GA | | | 12-0 | SPARE | D41734P | | 47 | | D41958P | CAP | Y | | 115-199 |
| 0104 | 22 | GA | | | 154-0 | SPARE | D41958P | | 43 | | D41686P | 18 | | | 115-199 |
| 0105 | 22 | GA | | | 68-0 | SPARE | D40006J | | 41 | | D41734P | 48 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0105 | 22 | | GA | | 24-0 | SPARE | | D41986P | | 3 | | D41734P | | 48 | | 115-199 |
| 0106 | 22 | | GA | | 22-0 | 26-15-11 | | D41986P | | 9 | | D41958P | | 36 | | 001-099 |
| 0106 | 22 | | GA | | 21-0 | 26-15-11 | | D41986P | | 9 | | D41958P | | 36 | | 115-199 |
| 0107 | 22 | | GA | | 68-0 | SPARE | | D40006J | | 42 | | D41734P | | 49 | | 001-099 |
| 0107 | 22 | | GA | | 24-0 | SPARE | | D42000P | | 19 | | D41734P | | 49 | | 115-199 |
| 0108 | 22 | | GA | | 23-0 | SPARE | | D42000P | | 20 | | D41734P | | 50 | | 001-099 |
| 0108 | 22 | | GA | | 24-0 | SPARE | | D42000P | | 20 | | D41734P | | 50 | | 115-199 |
| 0109 | 22 | | GA | | 68-0 | SPARE | | D40042J | | 5 | | D41986P | | 11 | | 115-199 |
| 0110 | 22 | | GA | | 15-0 | 32-44-11 | | D41734P | | 51 | | D41958P | | 44 | | 001-099 |
| 0110 | 22 | | GA | | 12-0 | 32-44-11 | | D41958P | | 44 | | D41734P | | 51 | | 115-199 |
| 0111 | 22 | | GA | | 15-0 | SPARE | | D41734P | | 52 | | D41958P | | 45 | | 001-099 |
| 0111 | 22 | | GA | | 12-0 | 32-44-11 | | D41958P | | 45 | | D41734P | | 52 | | 115-199 |
| 0112 | 22 | | GA | | 27-0 | 32-44-11 | | D42016P | | 19 | | D41958P | | 46 | | 001-099 |
| 0112 | 22 | | GA | | 26-0 | 32-44-11 | | D41958P | | 46 | | D42016P | | 19 | | 115-199 |
| 0113 | 22 | | GA | | 27-0 | 32-44-11 | | D42016P | | 20 | | D41958P | | 47 | | 001-099 |
| 0113 | 22 | | GA | | 26-0 | 32-44-11 | | D41958P | | 47 | | D42016P | | 22 | | 115-199 |
| 0114 | 22 | | GA | | 27-0 | 32-44-11 | | D42016P | | 21 | | D41958P | | 48 | | 001-099 |
| 0114 | 22 | | GA | | 26-0 | 32-44-11 | | D41958P | | 48 | | D42016P | | 21 | | 115-199 |
| 0115 | 22 | | GA | | 27-0 | 32-44-11 | | D42016P | | 22 | | D41958P | | 49 | | 001-099 |
| 0115 | 22 | | GA | | 26-0 | 32-44-11 | | D41958P | | 49 | | D42016P | | 20 | | 115-199 |
| 0116 | 22 | | GA | | 154-0 | 32-44-11 | | D41686P | | 14 | | D41958P | | 50 | | 115-199 |
| 0117 | 22 | | GA | | 21-0 | 26-16-11 | | D41986P | | 24 | | D42000P | | 22 | | ALL |
| 0118 | 24 | | GK | | 154-0 | SPARE | | D41958P | | 51 | | D41686P | | 20 | | 115-199 |
| 0119 | 24 | | GK | | 154-0 | SPARE | | D41958P | | 52 | | D41686P | | 21 | | 115-199 |
| 0120 | 22 | | GA | | 63-0 | 29-33-11 | | D40366J | | 4 | | D42016P | | 48 | | 001-099 |
| 0120 | 22 | | GA | | 136-0 | 29-33-11 | | D40366J | | 4 | | D41686P | | 25 | | 115-199 |
| 0121 | 22 | | GA | | 63-0 | 29-33-11 | | D40366J | | 5 | | D42016P | | 47 | | 001-099 |
| 0121 | 22 | | GA | | 136-0 | 29-33-11 | | D40366J | | 5 | | D41686P | | 26 | | 115-199 |
| 0122 | 22 | | GA | | 63-0 | 29-33-11 | | D40366J | | 8 | | D42016P | | 49 | | 001-099 |
| 0122 | 22 | | GA | | 136-0 | 29-33-11 | | D40366J | | 8 | | D41686P | | 27 | | 115-199 |
| 0127 | 22 | | GA | | 137-0 | 32-42-11 | | D41686P | | 33 | | D42016P | | 23 | | 115-199 |
| 0128 | 22 | | GA | | 137-0 | 32-42-11 | | D41686P | | 32 | | D42016P | | 24 | | 115-199 |
| 0129 | 20 | | GA | | 27-0 | 29-21-31 | | D42016P | | 29 | | D41958P | | 54 | | 001-099 |
| 0129 | 20 | | GA | | 26-0 | 29-21-31 | | D42016P | | 29 | | D41958P | | 54 | | 115-199 |
| 0130 | 22 | | GA | | 9-0 | 29-21-31 | | D03572 | | 8 | | TB0116Y | C006 | BJ | | 001-099 |
| 0130 | 18 | | GA | | 39-0 | 29-21-31 | | D03572 | | 8 | 18 | D41958P | | 53 | 18 | 115-199 |
| 0131 | 18 | | GA | | 41-0 | 29-21-31 | | D03572 | | 7 | 18 | D41958P | | 55 | 18 | 001-099 |
| 0131 | 18 | | GA | | 39-0 | 29-21-31 | | D03572 | | 7 | 18 | D41958P | | 55 | 18 | 115-199 |
| 0132 | 22 | | GA | | 48-0 | 29-21-31 | | D03572 | | 20 | | D42016P | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0133 | 22 | | GA | | 48-0 | 29-21-31 | D03572 | 40 | | | D42016P | 10 | | | ALL |
| 0135 | 22 | | GA | | 39-0 | SPARE | D41958P | 53 | | | TB0116Y | C006 | BJ | | 001-099 |
| 0136 | 20 | | GA | | 10-0 | 28-25-11 | D42016P | 26 | | | D40022P | 1 | | | ALL |
| 0137 | 20 | | GA | | 25-0 | 28-25-11 | D41986P | 8 | | | D40022P | 2 | | | ALL |
| 0138 | 12 | | GA | | 63-9 | 28-25-11 | D40350J | 27 | | | D40022P | 15 | | | 001-099 |
| 0138 | 12 | | GA | | 63-11 | 28-25-11 | D40350J | 27 | | | D40022P | 15 | | | 115-199 |
| 0139 | 22 | | GA | | 85-0 | 28-42-21 | D40350J | 5 | | | D41734P | 44 | | | ALL |
| 0141 | 24 | | GK | | 22-0 | 28-25-11 | D40022P | 5 | | | D41958P | 35 | | | 001-099 |
| 0141 | 24 | | GK | | 21-0 | 28-25-11 | D40022P | 5 | | | D41958P | 35 | | | 115-199 |
| 0145 | 20 | | GA | | 4-0 | 80-11-11 | D03572 | 28 | | | GD00604 | ST.. | 2 | | 001-099 |
| 0145 | 20 | | GA | | 5-0 | 80-11-11 | D03572 | 28 | | | GD00604 | ST.. | 2 | | 115-199 |
| 0146 | 22 | | GA | | 86-0 | 29-22-11 | D40350J | 12 | | | D41734P | 1 | | | 001-099 |
| 0146 | 22 | | GA | | 85-0 | 29-22-11 | D40350J | 12 | | | D41734P | 20 | | | 115-199 |
| 0147 | 22 | | GA | | 22-0 | SPARE | D41958P | 1 | | | D40022P | 10 | | | 001-099 |
| 0147 | 22 | | GA | | 21-0 | SPARE | D41958P | 1 | | | D40022P | 10 | | | 115-199 |
| 0148 | 24 | | GK | | 1-0 | 73-21-11 | D03572 | 22 | | | SM00001 | | 9 | | ALL |
| 0149 | 24 | | GK | | 1-0 | 73-21-11 | D03572 | 25 | | | SM00001 | | 9 | | ALL |
| 0152 | 22 | | GA | | 27-0 | 32-61-21 | D41958P | 31 | | | D42016P | 31 | | | 001-099 |
| 0152 | 22 | | GA | | 26-0 | 32-61-21 | D41958P | 31 | | | D42016P | 31 | | | 115-199 |
| 0153 | 20 | | GA | | 41-0 | 74-31-11 | D03572 | 31 | | | D41958P | 37 | | | 001-099 |
| 0153 | 20 | | GA | | 39-0 | 74-31-11 | D03572 | 31 | | | D41958P | 37 | | | 115-199 |
| 0154 | 20 | | GA | | 33-0 | 74-31-11 | D03572 | 29 | | | SM00003 | | 9 | | 001-099 |
| 0155 | 20 | | GA | | 11-0 | 74-31-11 | D41958P | 39 | | | SM00003 | | 9 | | 001-099 |
| 0156 | 20 | | GA | | 26-0 | 32-35-11 | D42016P | 27 | | | D41958P | 34 | | | 115-199 |
| 0158 | 20 | | GA | | 67-0 | SPARE | D40006J | 1 | | | D41734P | 33 | | | 115-199 |
| 0162 | 20 | | GA | | 40-0 | 74-31-11 | D03572 | 12 | | | D41958P | 29 | | | 001-099 |
| 0162 | 20 | | GA | | 39-0 | 74-31-11 | D03572 | 12 | | | D41958P | 29 | | | 115-199 |
| 0163 | 24 | | GK | | 17-0 | 78-36-11 | D41958P | 30 | | | D41734P | 24 | | | ALL |
| 0178 | 20 | | GA | | 65-0 | 78-36-11 | D40006J | 33 | | | D41958P | 43 | | | 003-099 |
| 1001 | 22 | | GT | BA | 64-0 | 29-33-11 | D40366J | 1 | VN | | D42138P | 1 | | | 001-099 |
| 1001 | 22 | | GT | BA | 136-0 | 29-33-11 | D40366J | 1 | VN | | D40464P | 1 | | | 115-199 |
| 1001Z | | | | BA | 0-0 | 29-33-11 | D40366J | = C1 | | | D42138P | = C1 | | | 001-099 |
| 1001Z | | | | BA | 0-0 | 29-33-11 | D40366J | = C1 | | | D40464P | = C1 | | | 115-199 |
| 1002 | 22 | | GT | BB | 64-0 | 29-33-11 | D41406J | 1 | VN | | D42132P | 1 | | | 001-099 |
| 1002 | 22 | | GT | BB | 136-0 | 29-33-11 | D41406J | 1 | VN | | D40480P | 1 | | | 115-199 |
| 1002Z | | | | BB | 0-0 | 29-33-11 | D41406J | = C1 | | | D42132P | = C1 | | | 001-099 |
| 1002Z | | | | BB | 0-0 | 29-33-11 | D41406J | = C1 | | | D40480P | = C1 | | | 115-199 |
| 1005 | 20 | | GE | T | 65-0 | 76-11-21 | D40006J | 19 | | | D41958P | 7 | | | 001-099 |
| 1005 | 20 | | GE | T | 63-0 | 76-11-21 | D40006J | 19 | | | D41958P | 7 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 1005Z | | | | T | 0-0 | 76-11-21 | D40006J | S/R | | | GD03612 | ST.. | E | | ALL |
| 2001B | 22 | GB | CC | | 46-0 | 78-36-11 | D42016P | 2 | | | D40268J | 2 | | | 001-099 |
| 2001B | 22 | GB | AG | | 46-0 | 78-36-11 | D40268J | 2 | | | D42016P | 2 | | | 115-199 |
| 2001R | 22 | GB | CC | | 0-0 | 78-36-11 | D42016P | 1 | | | D40268J | 1 | | | 001-099 |
| 2001R | 22 | GB | AG | | 0-0 | 78-36-11 | D40268J | 1 | | | D42016P | 1 | | | 115-199 |
| 2002B | 22 | GB | CD | | 46-0 | 78-36-11 | D42016P | 4 | | | D40268J | 4 | | | 001-099 |
| 2002B | 22 | GB | AH | | 46-0 | 78-36-11 | D40268J | 4 | | | D42016P | 4 | | | 115-199 |
| 2002R | 22 | GB | CD | | 0-0 | 78-36-11 | D42016P | 3 | | | D40268J | 3 | | | 001-099 |
| 2002R | 22 | GB | AH | | 0-0 | 78-36-11 | D40268J | 3 | | | D42016P | 3 | | | 115-199 |
| 2003B | 22 | GB | CE | | 46-0 | 78-36-11 | D42016P | 6 | | | D40268J | 6 | | | 001-099 |
| 2003B | 22 | GB | AJ | | 46-0 | 78-36-11 | D40268J | 6 | | | D42016P | 6 | | | 115-199 |
| 2003R | 22 | GB | CE | | 0-0 | 78-36-11 | D42016P | 5 | | | D40268J | 5 | | | 001-099 |
| 2003R | 22 | GB | AJ | | 0-0 | 78-36-11 | D40268J | 5 | | | D42016P | 5 | | | 115-199 |
| 2004B | 22 | GB | CF | | 46-0 | 78-36-11 | D42016P | 8 | | | D40268J | 8 | | | 001-099 |
| 2004B | 22 | GB | AK | | 46-0 | 78-36-11 | D40268J | 8 | | | D42016P | 8 | | | 115-199 |
| 2004R | 22 | GB | CF | | 0-0 | 78-36-11 | D42016P | 7 | | | D40268J | 7 | | | 001-099 |
| 2004R | 22 | GB | AK | | 0-0 | 78-36-11 | D40268J | 7 | | | D42016P | 7 | | | 115-199 |
| 2006B | 20 | GB | AM | | 66-0 | 31-31-51 | D40350J | 2 | | | D41956P | 13 | | | 001-099 |
| 2006B | 20 | GB | AM | | 66-0 | 31-31-31 | D40350J | 2 | | | D41956P | 13 | | | 115-199 |
| 2006R | 20 | GB | AM | | 0-0 | 31-31-51 | D40350J | 1 | | | D41956P | 12 | | | 001-099 |
| 2006R | 20 | GB | AM | | 0-0 | 31-31-31 | D40350J | 1 | | | D41956P | 12 | | | 115-199 |
| 2501B | 22 | GU | AS | | 67-0 | 79-34-11 | D41734P | 14 | | | D40006J | 31 | | | 001-099 |
| 2501B | 22 | GU | AF | | 67-0 | 79-34-11 | D40006J | 31 | | | D41734P | 14 | | | 115-199 |
| 2501R | 22 | GU | AS | | 0-0 | 79-34-11 | D41734P | 15 | | | D40006J | 32 | | | 001-099 |
| 2501R | 22 | GU | AF | | 0-0 | 79-34-11 | D40006J | 32 | | | D41734P | 15 | | | 115-199 |
| 2501Z | | | AS | | 0-0 | 79-34-11 | D41734P | 16 | | | D40006J | S/R | | | 001-099 |
| 2501Z | | | AF | | 0-0 | 79-34-11 | D40006J | S/R | | | D41734P | 16 | | | 115-199 |
| 2502B | 20 | GU | AN | | 66-0 | 31-31-51 | D40350J | 4 | | | D41956P | 2 | | | 001-099 |
| 2502B | 20 | GU | AN | | 66-0 | 31-31-31 | D40350J | 4 | | | D41956P | 2 | | | 115-199 |
| 2502R | 20 | GU | AN | | 0-0 | 31-31-51 | D40350J | 3 | | | D41956P | 1 | | | 001-099 |
| 2502R | 20 | GU | AN | | 0-0 | 31-31-31 | D40350J | 3 | | | D41956P | 1 | | | 115-199 |
| 2502Z | | | AN | | 0-0 | 31-31-51 | D40350J | S/R | | | D41956P | 3 | | | 001-099 |
| 2502Z | | | AN | | 0-0 | 31-31-31 | D40350J | S/R | | | D41956P | 3 | | | 115-199 |
| 2503B | 20 | GU | AP | | 66-0 | 31-31-51 | D40350J | 8 | | | D41956P | 5 | | | 001-099 |
| 2503B | 20 | GU | AP | | 66-0 | 31-31-31 | D40350J | 8 | | | D41956P | 5 | | | 115-199 |
| 2503R | 20 | GU | AP | | 0-0 | 31-31-51 | D40350J | 7 | | | D41956P | 4 | | | 001-099 |
| 2503R | 20 | GU | AP | | 0-0 | 31-31-31 | D40350J | 7 | | | D41956P | 4 | | | 115-199 |
| 2503Z | | | AP | | 0-0 | 31-31-51 | D40350J | S/R | | | D41956P | 6 | | | 001-099 |
| 2503Z | | | AP | | 0-0 | 31-31-31 | D40350J | S/R | | | D41956P | 6 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | | To | | | | | |
|------------|-------------|----|-------|--|------|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC (continued) | | | | | | | | | | | | |
| 2504B | 20 | GU | AQ | | 66-0 | 31-31-51 | D40350J | 10 | | | | D41956P | 8 | | | 001-099 |
| 2504B | 20 | GU | AQ | | 66-0 | 31-31-31 | D40350J | 10 | | | | D41956P | 8 | | | 115-199 |
| 2504R | 20 | GU | AQ | | 0-0 | 31-31-51 | D40350J | 9 | | | | D41956P | 7 | | | 001-099 |
| 2504R | 20 | GU | AQ | | 0-0 | 31-31-31 | D40350J | 9 | | | | D41956P | 7 | | | 115-199 |
| 2504Z | | | AQ | | 0-0 | 31-31-51 | D40350J | S/R | | | | D41956P | 9 | | | 001-099 |
| 2504Z | | | AQ | | 0-0 | 31-31-31 | D40350J | S/R | | | | D41956P | 9 | | | 115-199 |
| 2505B | 24 | G2 | AR | | 23-0 | 77-12-31 | D41734P | 38 | | | | D42000P | 12 | | | 001-099 |
| 2505B | 24 | G2 | AS | | 24-0 | 77-12-31 | D41734P | 38 | | | | D42000P | 12 | | | 115-199 |
| 2505R | 24 | G2 | AR | | 0-0 | 77-12-31 | D41734P | 37 | | | | D42000P | 11 | | | 001-099 |
| 2505R | 24 | G2 | AS | | 0-0 | 77-12-31 | D41734P | 37 | | | | D42000P | 11 | | | 115-199 |
| 2505Z | | | AR | | 0-0 | 77-12-31 | D41734P | 39 | | | | D42000P | 13 | | | 001-099 |
| 2505Z | | | AS | | 0-0 | 77-12-31 | D41734P | 39 | | | | D42000P | 13 | | | 115-199 |
| 2506B | 22 | GU | AT | | 67-0 | 79-34-11 | D41734P | 41 | | | | D40006J | 5 | | | ALL |
| 2506R | 22 | GU | AT | | 0-0 | 79-34-11 | D41734P | 53 | | | | D40006J | 6 | | | ALL |
| 2506Z | | | AT | | 0-0 | 79-34-11 | D41734P | 43 | | | | D40006J | S/R | | | ALL |
| 2507B | 22 | GU | CJ | | 67-0 | SPARE | D41734P | 45 | | | | D40006J | 1 | | | 001-099 |
| 2507R | 22 | GU | CJ | | 0-0 | SPARE | D41734P | 54 | | | | D40006J | 2 | | | 001-099 |
| 2507Z | | | CJ | | 0-0 | SPARE | D41734P | 55 | | | | D40006J | 4 | | | 001-099 |
| 2508B | 20 | GU | CK | | 67-0 | SPARE | D40006J | 2 | | | | D41734P | 46 | | | 115-199 |
| 2508R | 20 | GU | CK | | 0-0 | SPARE | D40006J | 3 | | | | D41734P | 54 | | | 115-199 |
| 2508Z | | | CK | | 0-0 | SPARE | D40006J | 4 | | | | D41734P | 55 | | | 115-199 |
| 3001B | 22 | GC | AB | | 67-0 | 73-31-11 | D40006J | 15 | | | | D41734P | 3 | | | 115-199 |
| 3001R | 22 | GC | AB | | 0-0 | 73-31-11 | D40006J | 14 | | | | D41734P | 2 | | | 115-199 |
| 3001Y | 22 | GC | AB | | 0-0 | 73-31-11 | D40006J | 16 | | | | D41734P | 4 | | | 115-199 |
| 3002B | 22 | GC | CG | | 67-0 | 79-31-11 | D41734P | 9 | | | | D40006J | 26 | | | 001-099 |
| 3002B | 22 | GC | AD | | 67-0 | 79-31-11 | D40006J | 26 | | | | D41734P | 9 | | | 115-199 |
| 3002R | 22 | GC | CG | | 0-0 | 79-31-11 | D41734P | 10 | | | | D40006J | 27 | | | 001-099 |
| 3002R | 22 | GC | AD | | 0-0 | 79-31-11 | D40006J | 27 | | | | D41734P | 10 | | | 115-199 |
| 3002Y | 22 | GC | CG | | 0-0 | 79-31-11 | D41734P | 8 | | | | D40006J | 25 | | | 001-099 |
| 3002Y | 22 | GC | AD | | 0-0 | 79-31-11 | D40006J | 25 | | | | D41734P | 8 | | | 115-199 |
| 3003B | 22 | GC | CH | | 68-0 | 79-32-11 | D41734P | 12 | | | | D40006J | 28 | | | 001-099 |
| 3003B | 22 | GC | AE | | 67-0 | 79-32-11 | D40006J | 28 | | | | D41734P | 12 | | | 115-199 |
| 3003R | 22 | GC | CH | | 0-0 | 79-32-11 | D41734P | 11 | | | | D40006J | 29 | | | 001-099 |
| 3003R | 22 | GC | AE | | 0-0 | 79-32-11 | D40006J | 29 | | | | D41734P | 11 | | | 115-199 |
| 3003Y | 22 | GC | CH | | 0-0 | 79-32-11 | D41734P | 13 | | | | D40006J | 30 | | | 001-099 |
| 3003Y | 22 | GC | AE | | 0-0 | 79-32-11 | D40006J | 30 | | | | D41734P | 13 | | | 115-199 |
| 3004B | 22 | GC | CB | | 68-0 | 73-31-11 | D41734P | 3 | | | | D40006J | 15 | | | 001-099 |
| 3004R | 22 | GC | CB | | 0-0 | 73-31-11 | D41734P | 2 | | | | D40006J | 14 | | | 001-099 |
| 3004Y | 22 | GC | CB | | 0-0 | 73-31-11 | D41734P | 4 | | | | D40006J | 16 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4210 | 286N4210 | | | E/E SHELF DISC TO LEFT WING BODY/WHEEL WELL DISC (continued) | | | | | | | | | | | |
| YAAA | | | | | 0-0 | 26-11-12 | D40042J | | S/R | | GD03003 | ST.. | E | * | 001-099 |
| YAAA | | | | | 0-0 | 73-31-11 | GD03003 | | ST.. | E | | S/R | | | 115-199 |
| YAAB | | | | | 0-0 | 29-32-11 | D40006J | | S/R | | GD03003 | ST.. | E | * | 001-099 |
| YAAC | | | | | 0-0 | 78-36-11 | D40268J | | S/R | | GD03003 | ST.. | E | * | 001-099 |
| YAAD | | | | | 0-0 | 26-18-11 | D40478J | | S/R | | GD03003 | ST.. | E | * | 001-099 |
| YAAD | | | | | 0-0 | 26-18-11 | GD03003 | | ST.. | E | * | S/R | | | 115-199 |
| YAAE | | | | | 0-0 | 78-36-11 | GD03003 | | ST.. | E | * | S/R | | | 115-199 |
| YAAF | | | | | 0-0 | 26-12-11 | GD03003 | | ST.. | E | * | S/R | | | 115-199 |
| W4212 | 286N4212 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - L2 | | | | | | | | | | | |
| 0001 | 20 | | GA | | 77-0 | 32-12-12 | D41634P | | 4 | | D40362J | | 15 | | ALL |
| 0002 | 20 | | GA | | 77-0 | 32-12-12 | D41634P | | 5 | | D40362J | | 19 | | ALL |
| 0003 | 22 | | GA | | 64-0 | 27-58-11 | D41690P | | 8 | | D40944P | | 8 | | 001-099 |
| 0003 | 22 | | GA | | 58-0 | 27-58-11 | D41690P | | 8 | | D40944J | | 8 | | 115-199 |
| 0004 | 22 | | GA | | 64-0 | 27-58-11 | D41690P | | 7 | | D40944P | | 7 | | 001-099 |
| 0004 | 22 | | GA | | 58-0 | 27-58-11 | D41690P | | 7 | | D40944J | | 7 | | 115-199 |
| 0005 | 22 | | GA | | 64-0 | 27-58-11 | D41690P | | 6 | | D40944P | | 6 | | 001-099 |
| 0005 | 22 | | GA | | 58-0 | 27-58-11 | D41690P | | 6 | | D40944J | | 6 | | 115-199 |
| 0008 | 20 | | GA | | 79-0 | 29-31-11 | D41722P | | 4 | | D40362J | | 9 | | 001-099 |
| 0008 | 20 | | GA | | 80-0 | 29-31-11 | D41722P | | 4 | | D40362J | | 9 | | 115-199 |
| 0012 | 22 | | GA | | 26-0 | 32-09-12 | D41794P | | 2 | | D41634P | | 15 | | 001-099 |
| 0012 | 22 | | GA | | 27-0 | 32-09-12 | D41794P | | 2 | | D41634P | | 15 | | 115-199 |
| 0013 | 22 | | GA | | 26-0 | 32-09-12 | D41794P | | 3 | | D41634P | | 14 | | 001-099 |
| 0013 | 22 | | GA | | 27-0 | 32-09-12 | D41794P | | 3 | | D41634P | | 14 | | 115-199 |
| 0014 | 22 | | GA | | 26-0 | SPARE | D41794P | | 1 | | D41634P | | 19 | | 001-099 |
| 0014 | 22 | | GA | | 27-0 | SPARE | D41794P | | 1 | | D41634P | | 16 | | 115-199 |
| 0015 | 22 | | GA | | 40-0 | SPARE | D41654P | | 19 | | D42076J | | 11 | | 001-099 |
| 0015 | 22 | | GA | | 54-0 | SPARE | D41634P | | 8 | | D42076J | | 11 | | 115-199 |
| 0016 | 22 | | GA | | 53-0 | SPARE | D41634P | | 18 | | D42076J | | 12 | | 001-099 |
| 0016 | 22 | | GA | | 54-0 | SPARE | D41634P | | 9 | | D42076J | | 12 | | 115-199 |
| 0017 | 22 | | GA | | 60-0 | SPARE | D41654P | | 17 | | D40944P | | 4 | | 001-099 |
| 0017 | 22 | | GA | | 59-0 | SPARE | D41654P | | 17 | | D40944J | | 4 | | 115-199 |
| 0018 | 22 | | GA | | 60-0 | SPARE | D41654P | | 18 | | D40944P | | 5 | | 001-099 |
| 0018 | 22 | | GA | | 59-0 | SPARE | D41654P | | 18 | | D40944J | | 5 | | 115-199 |
| 0019 | 20 | | GA | | 79-0 | SPARE | D41722P | | 5 | | D40362J | | 22 | | 001-099 |
| 0019 | 20 | | GA | | 80-0 | SPARE | D41722P | | 5 | | D40362J | | 22 | | 115-199 |
| 0020 | 22 | | GA | | 69-0 | 29-11-22 | D40362J | | 18 | | D41690P | | 1 | | 001-099 |
| 0020 | 20 | | GA | | 64-0 | 29-11-22 | D40362J | | 18 | | D41690P | | 1 | | 115-199 |
| 0021 | 22 | | GA | | 19-0 | 29-11-22 | D41794P | | 9 | | D41690P | | 2 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|---|---------|----------|---------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4212 | 286N4212 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - L2 (continued) | | | | | | | | | | |
| 0021 | 20 | | GA | | 14-0 | 29-11-22 | D41794P | | 9 | D41690P | | 2 | | 115-199 |
| 0022 | 22 | | GA | | 19-0 | 29-11-22 | D41690P | | 3 | D41794P | | 5 | | 001-099 |
| 2001B | 20 | | GB | AA | 70-0 | 32-09-11 | D41634P | | 6 | SP01250 | | | 9 | 001-099 |
| 2001B | 20 | | GB | AA | 73-0 | 32-09-11 | D41634P | | 6 | SP01250 | | | 9 | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 32-09-11 | D41634P | | 7 | SP01252 | | | 9 | ALL |
| 2002B | 24 | | GL | AB | 68-0 | 32-61-22 | D41634P | | 23 | SM00002 | | | 9 | 001-099 |
| 2002B | 24 | | GL | AB | 70-0 | 32-61-22 | D41634P | | 23 | SM00002 | | | 9 | 115-199 |
| 2002R | 24 | | GL | AB | 0-0 | 32-61-22 | D41634P | | 21 | SM00001 | | | 9 | ALL |
| 2003B | 22 | | GB | AC | 77-0 | 32-61-13 | D41634P | | 10 | D40362J | | 21 | | ALL |
| 2003R | 22 | | GB | AC | 0-0 | 32-61-13 | D41634P | | 11 | D40362J | | 17 | | ALL |
| 2004B | 22 | | GB | AD | 77-0 | 32-61-13 | D41634P | | 12 | D40362J | | 28 | | ALL |
| 2004R | 22 | | GB | AD | 0-0 | 32-61-13 | D41634P | | 13 | D40362J | | 25 | | ALL |
| 2005B | 22 | | GB | AE | 40-0 | 27-51-41 | D41654P | | 8 | D42076J | | 3 | | ALL |
| 2005R | 22 | | GB | AE | 0-0 | 27-51-41 | D41654P | | 7 | D42076J | | 2 | | ALL |
| 2006B | 22 | | GB | AF | 60-0 | 27-51-41 | D41654P | | 2 | D40944P | | 10 | | 001-099 |
| 2006B | 22 | | GB | AF | 59-0 | 27-51-41 | D41654P | | 2 | D40944J | | 10 | | 115-199 |
| 2006R | 22 | | GB | AF | 0-0 | 27-51-41 | D41654P | | 1 | D40944P | | | 9 | 001-099 |
| 2006R | 22 | | GB | AF | 0-0 | 27-51-41 | D41654P | | 1 | D40944J | | | 9 | 115-199 |
| 2007B | 20 | | GB | EC | 69-0 | 29-31-11 | D40362J | | 10 | D41794P | | | 4 | ALL |
| 2007R | 20 | | GB | EC | 0-0 | 29-31-11 | D40362J | | 11 | D41794P | | | 6 | ALL |
| 2502B | 22 | | GU | BA | 72-0 | 28-21-21 | D41634P | | 1 | D40944P | | | 2 | 001-099 |
| 2502B | 22 | | GU | BA | 71-0 | 28-21-21 | D41634P | | 1 | D40944J | | | 2 | 115-199 |
| 2502R | 22 | | GU | BA | 0-0 | 28-21-21 | D41634P | | 2 | D40944P | | | 1 | 001-099 |
| 2502R | 22 | | GU | BA | 0-0 | 28-21-21 | D41634P | | 2 | D40944J | | | 1 | 115-199 |
| 2502Z | | | | BA | 0-0 | 28-21-21 | D41634P | | 3 | D40944P | | | 3 | 001-099 |
| 2502Z | | | | BA | 0-0 | 28-21-21 | D41634P | | 3 | D40944J | | | 3 | 115-199 |
| 2503B | 20 | | GU | DA | 77-0 | 23-41-12 | D41634P | | 8 | D40362J | | 13 | | 001-099 |
| 2503R | 20 | | GU | DA | 0-0 | 23-41-12 | D41634P | | 9 | D40362J | | 12 | | 001-099 |
| 2503Z | | | | DA | 0-0 | 23-41-12 | D41634P | | 16 | D40362J | | 16 | | 001-099 |
| 2504B | 20 | | GF | AG | 10-0 | 32-61-22 | SM00002 | | 9 | D40432J | | | 2 | 001-099 |
| 2504B | 20 | | GF | AG | 8-0 | 32-61-22 | SM00002 | | 9 | D40432J | | | 2 | 115-199 |
| 2504R | 20 | | GF | AG | 0-0 | 32-61-22 | SM00001 | | 9 | D40432J | | | 1 | ALL |
| 2504Z | | | | AG | 0-0 | 32-61-22 | SM00002 | | 9 | D40432J | | DED | | ALL |
| 3002B | 18 | | GC | CB | 55-0 | 28-22-11 | D41722P | | 3 | D42076J | | 10 | | 001-099 |
| 3002B | 18 | | GC | CB | 57-0 | 28-22-11 | D41722P | | 3 | D42076J | | 10 | | 115-199 |
| 3002R | 18 | | GC | CB | 0-0 | 28-22-11 | D41722P | | 1 | D42076J | | | 8 | ALL |
| 3002Y | 18 | | GC | CB | 0-0 | 28-22-11 | D41722P | | 2 | D42076J | | | 9 | ALL |
| 3501B | 20 | | GV | DA | 77-0 | 23-41-12 | D41634P | | 28 | D40362J | | 13 | | 115-199 |
| 3501R | 20 | | GV | DA | 0-0 | 23-41-12 | D41634P | | 29 | D40362J | | 12 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4212 | 286N4212 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - L2 (continued) | | | | | | | | | | | |
| 3501Y | 20 | | GV | DA | 0-0 | 23-41-12 | D41634P | 30 | | | D40362J | 14 | | | 115-199 |
| 3501Z | | | | DA | 0-0 | 23-41-12 | D41634P | 31 | | | D40362J | 16 | | | 115-199 |
| 3502B | 18 | | GV | AI | 90-0 | 27-62-11 | D40442J | 15 | | | D42062P | 14 | | | 001-099 |
| 3502B | 18 | | GV | AH | 90-0 | 27-62-11 | D40442J | 15 | | | D42062P | 14 | | | 115-199 |
| 3502R | 18 | | GV | AI | 0-0 | 27-62-11 | D40442J | 16 | | | D42062P | 13 | | | 001-099 |
| 3502R | 18 | | GV | AH | 0-0 | 27-62-11 | D40442J | 16 | | | D42062P | 13 | | | 115-199 |
| 3502Y | 18 | | GV | AI | 0-0 | 27-62-11 | D40442J | 19 | | | D42062P | 6 | | | 001-099 |
| 3502Y | 18 | | GV | AH | 0-0 | 27-62-11 | D40442J | 19 | | | D42062P | 6 | | | 115-199 |
| 3502Z | | | | AI | 0-0 | 27-62-11 | D40442J | S/R | | | D42062P | 11 | | | 001-099 |
| 3502Z | | | | AH | 0-0 | 27-62-11 | D40442J | S/R | | | D42062P | 11 | | | 115-199 |
| 4001B | 22 | | GD | EA | 40-0 | 27-51-41 | D41654P | 10 | | | D42076J | 5 | | | ALL |
| 4001G | 22 | | GD | EA | 0-0 | 27-51-41 | D41654P | 12 | | | D42076J | 7 | | | ALL |
| 4001R | 22 | | GD | EA | 0-0 | 27-51-41 | D41654P | 9 | | | D42076J | 4 | | | ALL |
| 4001Y | 22 | | GD | EA | 0-0 | 27-51-41 | D41654P | 11 | | | D42076J | 6 | | | ALL |
| 4002B | 22 | | GD | EB | 60-0 | 27-51-41 | D41654P | 4 | | | D40944P | 12 | | | 001-099 |
| 4002B | 22 | | GD | EB | 59-0 | 27-51-41 | D41654P | 4 | | | D40944J | 12 | | | 115-199 |
| 4002G | 22 | | GD | EB | 0-0 | 27-51-41 | D41654P | 6 | | | D40944P | 14 | | | 001-099 |
| 4002G | 22 | | GD | EB | 0-0 | 27-51-41 | D41654P | 6 | | | D40944J | 14 | | | 115-199 |
| 4002R | 22 | | GD | EB | 0-0 | 27-51-41 | D41654P | 3 | | | D40944P | 11 | | | 001-099 |
| 4002R | 22 | | GD | EB | 0-0 | 27-51-41 | D41654P | 3 | | | D40944J | 11 | | | 115-199 |
| 4002Y | 22 | | GD | EB | 0-0 | 27-51-41 | D41654P | 5 | | | D40944P | 13 | | | 001-099 |
| 4002Y | 22 | | GD | EB | 0-0 | 27-51-41 | D41654P | 5 | | | D40944J | 13 | | | 115-199 |
| YAAA | | | | | 0-0 | 27-51-41 | D42076J | S/R | | | GD02560 | ST.. | E | | 001-099 |
| YAAA | | | | | 0-0 | 27-51-41 | D40944J | S/R | | | GD02604 | ST.. | E | * | 115-199 |
| YAAB | | | | | 0-0 | 27-51-41 | D40944P | S/R | | | GD02604 | ST.. | E | * | 001-099 |
| YAAC | | | | | 0-0 | 27-51-41 | GD02560 | ST.. | E | | D42076J | S/R | | | 115-199 |
| YAAD | | | | | 0-0 | 32-61-22 | D40432J | S/R | | | GD02604 | ST.. | E | * | 001-099 |
| YAAD | | | | | 0-0 | 32-61-12 | D40432J | S/R | | | GD02604 | ST.. | E | * | 115-199 |
| YAAE | | | | | 0-0 | 27-62-11 | D40442J | S/R | | | GD02741 | ST.. | E | | ALL |
| W4216 | 286N4216 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A | | | | | | | | | | | |
| 0001 | 22 | | GA | | 10-0 | 24-41-11 | D41730P | 10 | | | D41658P | 7 | | | 001-099 |
| 0001 | 22 | | GA | | 9-0 | 24-41-11 | D41730P | 10 | | | D41658P | 7 | | | 115-199 |
| 0002 | 22 | | GA | | 27-0 | 32-09-12 | D41614P | 44 | | | D41616P | 11 | | | 001-099 |
| 0002 | 22 | | GA | | 28-0 | 32-09-12 | D41614P | 44 | | | D41616P | 11 | | | 115-199 |
| 0003 | 22 | | GA | | 27-0 | 32-09-12 | D41614P | 45 | | | D41616P | 12 | | | 001-099 |
| 0003 | 22 | | GA | | 28-0 | 32-09-12 | D41614P | 45 | | | D41616P | 12 | | | 115-199 |
| 0004 | 22 | | GA | | 27-0 | 32-09-12 | D41614P | 46 | | | D41616P | 13 | | | 001-099 |
| 0004 | 22 | | GA | | 28-0 | 32-09-12 | D41614P | 46 | | | D41616P | 13 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4216 | 286N4216 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | |
| 0005 | 22 | | GA | | 27-0 | 32-09-12 | D41614P | | 47 | | D41616P | | 14 | | 001-099 |
| 0005 | 22 | | GA | | 28-0 | 32-09-12 | D41614P | | 47 | | D41616P | | 14 | | 115-199 |
| 0006 | 22 | | GA | | 27-0 | 32-09-12 | D41614P | | 48 | | D41616P | | 15 | | 001-099 |
| 0006 | 22 | | GA | | 28-0 | 32-09-12 | D41614P | | 48 | | D41616P | | 15 | | 115-199 |
| 0007 | 22 | | GA | | 27-0 | 32-09-12 | D41614P | | 49 | | D41616P | | 16 | | 001-099 |
| 0007 | 22 | | GA | | 28-0 | 32-09-12 | D41614P | | 49 | | D41616P | | 16 | | 115-199 |
| 0008 | 20 | | GA | | 28-0 | | SPARE | | 50 | | D41616P | | 17 | | 115-199 |
| 0009 | 22 | | GA | | 27-0 | 32-09-12 | D41614P | | 51 | | D41616P | | 18 | | 001-099 |
| 0009 | 22 | | GA | | 28-0 | 32-09-12 | D41614P | | 51 | | D41616P | | 18 | | 115-199 |
| 0010 | 22 | | GA | | 27-0 | 76-11-21 | D42060P | | 1 | | D41616P | | 3 | | ALL |
| 0011 | 22 | | GA | | 27-0 | 32-61-12 | D42060P | | 3 | | D41616P | | 19 | | ALL |
| 0012 | 22 | | GA | | 27-0 | 32-61-12 | D42060P | | 4 | | D41616P | | 20 | | ALL |
| 0013 | 22 | | GA | | 27-0 | 32-61-12 | D42060P | | 5 | | D41616P | | 21 | | ALL |
| 0014 | 22 | | GA | | 27-0 | | SPARE | | 6 | | D41616P | | 22 | | ALL |
| 0015 | 22 | | GA | | 27-0 | 32-61-12 | D42060P | | 7 | | D41616P | | 23 | | ALL |
| 0016 | 22 | | GA | | 27-0 | 27-23-11 | D42060P | | 8 | | D41616P | | 24 | | 115-199 |
| 0017 | 22 | | GA | | 27-0 | 27-23-11 | D42060P | | 9 | | D41616P | | 25 | | 115-199 |
| 0019 | 20 | | GA | | 74-0 | 27-62-11 | D41616P | | 33 | | D40360J | | 4 | | 001-099 |
| 0019 | 20 | | GA | | 73-0 | 27-62-11 | D41616P | | 33 | | D40360J | | 4 | | 115-199 |
| 0020 | 20 | | GA | | 74-0 | 27-62-11 | D41616P | | 34 | | D40360J | | 5 | | 001-099 |
| 0020 | 20 | | GA | | 73-0 | 27-62-11 | D41616P | | 34 | | D40360J | | 5 | | 115-199 |
| 0021 | 20 | | GA | | 57-0 | 28-21-11 | D41718P | | 3 | | D40332J | | 17 | | 001-099 |
| 0021 | 20 | | GA | | 59-0 | 28-21-11 | D41718P | | 3 | | D40332J | | 17 | | 115-199 |
| 0022 | 22 | | GA | | 57-0 | 28-21-21 | D41718P | | 8 | | D40332J | | 15 | | 001-099 |
| 0022 | 20 | | GA | | 59-0 | 28-21-21 | D41718P | | 8 | | D40332J | | 15 | | 115-199 |
| 0023 | 20 | | GA | | 57-0 | 28-21-22 | D41718P | | 13 | | D40332J | | 9 | | 001-099 |
| 0023 | 20 | | GA | | 59-0 | 28-21-22 | D41718P | | 13 | | D40332J | | 9 | | 115-199 |
| 0024 | 20 | | GA | | 57-0 | 28-21-22 | D41718P | | 14 | | D40332J | | 8 | | 001-099 |
| 0024 | 20 | | GA | | 59-0 | 28-21-22 | D41718P | | 14 | | D40332J | | 8 | | 115-199 |
| 0025 | 20 | | GA | | 57-0 | 28-21-22 | D41718P | | 15 | | D40332J | | 7 | | 001-099 |
| 0025 | 20 | | GA | | 59-0 | 28-21-22 | D41718P | | 15 | | D40332J | | 7 | | 115-199 |
| 0026 | 22 | | GA | | 77-0 | 28-26-11 | D41718P | | 26 | | D40930P | | 22 | | 001-099 |
| 0026 | 20 | | GA | | 77-0 | 28-26-11 | D41718P | | 26 | | D40930J | | 22 | | 115-199 |
| 0027 | 22 | | GA | | 77-0 | 28-26-11 | D41718P | | 27 | | D40930P | | 21 | | 001-099 |
| 0027 | 20 | | GA | | 77-0 | 28-26-11 | D41718P | | 27 | | D40930J | | 21 | | 115-199 |
| 0028 | 22 | | GA | | 77-0 | 28-26-11 | D41718P | | 28 | | D40930P | | 20 | | 001-099 |
| 0028 | 20 | | GA | | 77-0 | 28-26-11 | D41718P | | 28 | | D40930J | | 20 | | 115-199 |
| 0029 | 20 | | GA | | 79-0 | 32-09-12 | D41614P | | 52 | | D40360J | | 18 | | 001-099 |
| 0029 | 20 | | GA | | 80-0 | 32-09-12 | D41614P | | 52 | | D40360J | | 18 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4216 | 286N4216 | | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | | |
| 0030 | 22 | | GA | | 68-0 | 28-42-11 | D41720P | | 1 | | | D40358J | | 7 | | 001-099 | |
| 0030 | 20 | | GA | | 67-0 | 28-42-11 | D41720P | | 1 | | | D40358J | | 7 | | 115-199 | |
| 0031 | 22 | | GA | | 24-0 | 76-11-21 | D41616P | | 7 | | | D41730P | | 1 | | 115-199 | |
| 0033 | 20 | | GA | | 34-0 | 28-21-22 | D41614P | | 37 | | | D41718P | | 9 | | 001-099 | |
| 0033 | 20 | | GA | | 35-0 | 28-21-22 | D41614P | | 37 | | | D41718P | | 9 | | 115-199 | |
| 0034 | 20 | | GA | | 34-0 | 28-21-22 | D41614P | | 34 | | | D41718P | | 10 | | 001-099 | |
| 0034 | 20 | | GA | | 35-0 | 28-21-22 | D41614P | | 34 | | | D41718P | | 10 | | 115-199 | |
| 0035 | 20 | | GA | | 34-0 | 28-21-22 | D41614P | | 35 | | | D41718P | | 11 | | 001-099 | |
| 0035 | 20 | | GA | | 35-0 | 28-21-22 | D41614P | | 35 | | | D41718P | | 11 | | 115-199 | |
| 0036 | 20 | | GA | | 34-0 | 28-21-22 | D41614P | | 36 | | | D41718P | | 12 | | 001-099 | |
| 0036 | 20 | | GA | | 35-0 | 28-21-22 | D41614P | | 36 | | | D41718P | | 12 | | 115-199 | |
| 0037 | 24 | | GK | | 31-0 | 33-42-11 | D42060P | | 10 | | | D41718P | | 31 | | 001-099 | |
| 0037 | 20 | | GA | | 33-0 | 33-42-11 | D42060P | | 10 | | | D41718P | | 31 | | 115-199 | |
| 0038 | 20 | | GA | | 34-0 | 28-21-11 | D41614P | | 28 | | | D41718P | | 7 | | 001-099 | |
| 0038 | 22 | | GA | | 35-0 | 28-21-11 | D41614P | | 28 | | | D41718P | | 7 | | 115-199 | |
| 0039 | 22 | | GA | | 10-0 | 27-23-11 | SM00001 | | | 9 | | D41720P | | 4 | | 001-099 | |
| 0039 | 22 | | GA | | 24-0 | 27-23-11 | D42060P | | 11 | | | D41720P | | 4 | | 115-199 | |
| 0041 | 20 | | GA | | 56-0 | 28-41-11 | D41614P | | 1 | | | D40334J | | 9 | | 115-199 | |
| 0042 | 20 | | GA | | 54-0 | 28-41-11 | D41614P | | 2 | | | D40334J | | 14 | | 001-099 | |
| 0042 | 20 | | GA | | 56-0 | 28-41-11 | D41614P | | 2 | | | D40334J | | 14 | | 115-199 | |
| 0043 | 20 | | GA | | 56-0 | SPARE | D41614P | | 3 | | | D40334J | | 15 | | 115-199 | |
| 0044 | 20 | | GA | | 54-0 | 28-41-11 | D41614P | | 4 | | | D40334J | | 20 | | 001-099 | |
| 0044 | 20 | | GA | | 56-0 | 28-41-11 | D41614P | | 4 | | | D40334J | | 20 | | 115-199 | |
| 0045 | 20 | | GA | | 56-0 | SPARE | D41614P | | CAP | Y | | D40334J | | 21 | | 115-199 | |
| 0046 | 20 | | GA | | 20-0 | 27-62-11 | D41616P | | 9 | | | D41720P | | 5 | | 001-099 | |
| 0046 | 20 | | GA | | 21-0 | 27-62-11 | D41616P | | 9 | | | D41720P | | 5 | | 115-199 | |
| 0047 | 22 | | GA | | 29-0 | 28-21-23 | D40334J | | 47 | | | D40930P | | 30 | | 001-099 | |
| 0047 | 20 | | GA | | 29-0 | 28-21-23 | D40334J | | 47 | | | D40930J | | 30 | | 115-199 | |
| 0048 | 22 | | GA | | 10-0 | 28-21-23 | D40334J | | 46 | | | SP00516 | | | 9 | 001-099 | |
| 0048 | 20 | | GA | | 10-0 | 28-21-23 | D40334J | | 46 | | | SP00516 | | | 9 | 115-199 | |
| 0049 | 22 | | GA | | 10-0 | 28-21-23 | D40334J | | 45 | | | SP00508 | | | 9 | 001-099 | |
| 0049 | 20 | | GA | | 10-0 | 28-21-23 | D40334J | | 45 | | | SP00508 | | | 9 | 115-199 | |
| 0050 | 22 | | GA | | 10-0 | 28-21-23 | D40334J | | 44 | | | SP00512 | | | 9 | 001-099 | |
| 0050 | 20 | | GA | | 10-0 | 28-21-23 | D40334J | | 44 | | | SP00512 | | | 9 | 115-199 | |
| 0051 | 22 | | GA | | 54-0 | 28-21-21 | D41614P | | 29 | | | D40332J | | 16 | | 001-099 | |
| 0051 | 20 | | GA | | 56-0 | 28-21-21 | D41614P | | 29 | | | D40332J | | 16 | | 115-199 | |
| 0058 | 22 | | GA | | 63-0 | 28-42-11 | D41720P | | 2 | | | D40930P | | 23 | | 001-099 | |
| 0058 | 20 | | GA | | 64-0 | 28-42-11 | D41720P | | 2 | | | D40930J | | 23 | | 115-199 | |
| 0059 | 22 | | GA | | 74-0 | 27-23-11 | D41616P | | 25 | | | D40360J | | 1 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4216 | 286N4216 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | |
| 0059 | 22 | | GA | | 79-0 | 27-23-11 | D42060P | | 12 | | D40360J | 1 | | | 115-199 |
| 0060 | 22 | | GA | | 15-0 | 27-23-11 | D41616P | | 24 | | SM00001 | | 9 | | 001-099 |
| 0060 | 22 | | GA | | 79-0 | 27-23-11 | D42060P | | 13 | | D40360J | 3 | | | 115-199 |
| 0061 | 22 | | GA | | 74-0 | 27-23-11 | D41616P | | 26 | | D40360J | 2 | | | 001-099 |
| 0061 | 22 | | GA | | 73-0 | 27-23-11 | D41616P | | 26 | | D40360J | 2 | | | 115-199 |
| 0062 | 20 | | GA | | 77-0 | 28-21-23 | D41718P | | 19 | | D40930P | 32 | | | 001-099 |
| 0062 | 20 | | GA | | 77-0 | 28-21-23 | D41718P | | 19 | | D40930J | 32 | | | 115-199 |
| 0063 | 20 | | GA | | 52-0 | 28-21-23 | D41718P | | 17 | | SP01016 | | 9 | | ALL |
| 0064 | 20 | | GA | | 52-0 | 28-21-23 | D41718P | | 18 | | SP01010 | | 9 | | ALL |
| 0065 | 20 | | GA | | 52-0 | 28-21-23 | D41718P | | 20 | | SP01012 | | 9 | | ALL |
| 0067 | 20 | | GA | | 57-0 | 28-26-11 | D41718P | | 21 | | D40332J | 2 | | | 001-099 |
| 0067 | 20 | | GA | | 59-0 | 28-26-11 | D41718P | | 21 | | D40332J | 2 | | | 115-199 |
| 0068 | 20 | | GA | | 57-0 | 28-26-11 | D41718P | | 22 | | D40332J | 3 | | | 001-099 |
| 0068 | 20 | | GA | | 59-0 | 28-26-11 | D41718P | | 22 | | D40332J | 3 | | | 115-199 |
| 0069 | 20 | | GA | | 57-0 | 28-26-11 | D41718P | | 23 | | D40332J | 4 | | | 001-099 |
| 0069 | 20 | | GA | | 59-0 | 28-26-11 | D41718P | | 23 | | D40332J | 4 | | | 115-199 |
| 0070 | 20 | | GA | | 57-0 | 28-26-11 | D41718P | | 24 | | D40332J | 5 | | | 001-099 |
| 0070 | 20 | | GA | | 59-0 | 28-26-11 | D41718P | | 24 | | D40332J | 5 | | | 115-199 |
| 0071 | 20 | | GA | | 57-0 | 28-26-11 | D41718P | | 25 | | D40332J | 6 | | | 001-099 |
| 0071 | 20 | | GA | | 59-0 | 28-26-11 | D41718P | | 25 | | D40332J | 6 | | | 115-199 |
| 0072 | 20 | | GA | | 50-0 | 28-21-11 | D41616P | | 40 | | D40334J | 5 | | | 001-099 |
| 0072 | 20 | | GA | | 59-0 | 28-21-11 | D41718P | | 4 | | D40334J | 5 | | | 115-199 |
| 0073 | 22 | | GA | | 56-0 | SPARE | D41718P | | 5 | | D40334J | 26 | | | 001-099 |
| 0073 | 22 | | GA | | 59-0 | 28-21-11 | D41718P | | 5 | | D40334J | 6 | | | 115-199 |
| 0074 | 22 | | GA | | 57-0 | 28-21-11 | D41718P | | 6 | | D40334J | 7 | | | 001-099 |
| 0074 | 22 | | GA | | 59-0 | 28-21-11 | D41718P | | 6 | | D40334J | 7 | | | 115-199 |
| 0075 | 24 | | GK | | 20-0 | 30-31-12 | D41616P | | 1 | | D41720P | 3 | | | 001-099 |
| 0075 | 24 | | GK | | 21-0 | 30-31-12 | D41616P | | 1 | | D41720P | 3 | | | 115-199 |
| 0076 | 24 | | GK | | 20-0 | 30-31-12 | D41616P | | 4 | | D41720P | 6 | | | 001-099 |
| 0076 | 24 | | GK | | 21-0 | 30-31-12 | D41616P | | 4 | | D41720P | 6 | | | 115-199 |
| 0077 | 20 | | GA | | 77-0 | 28-41-31 | D41718P | | 1 | | D40930J | 7 | | | 115-199 |
| 0078 | 20 | | GA | | 77-0 | 28-41-41 | D41718P | | 2 | | D40930J | 11 | | | 115-199 |
| 0079 | 22 | | GA | | 20-0 | SPARE | D41616P | | 27 | | D41720P | 7 | | | 001-099 |
| 0079 | 22 | | GA | | 21-0 | SPARE | D41616P | | 27 | | D41720P | 7 | | | 115-199 |
| 0080 | 24 | | GK | | 20-0 | 30-31-12 | D41616P | | 28 | | D41720P | 8 | | | 001-099 |
| 0080 | 24 | | GK | | 21-0 | 30-31-12 | D41616P | | 28 | | D41720P | 8 | | | 115-199 |
| 0081 | 24 | | GK | | 20-0 | 30-31-12 | D41616P | | 29 | | D41720P | 9 | | | 001-099 |
| 0081 | 24 | | GK | | 21-0 | 30-31-12 | D41616P | | 29 | | D41720P | 9 | | | 115-199 |
| 0082 | 24 | | GK | | 21-0 | SPARE | D41616P | | 39 | | D41720P | 20 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4216 | 286N4216 | | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | |
| 0083 | 24 | | GK | | 21-0 | SPARE | | D41616P | 40 | | | D41720P | 21 | | | 115-199 |
| 0084 | 24 | | GK | | 20-0 | 30-32-11 | | D41616P | 32 | | | D41720P | 12 | | | 001-099 |
| 0084 | 24 | | GK | | 21-0 | 30-32-11 | | D41616P | 32 | | | D41720P | 12 | | | 115-199 |
| 0085 | 20 | | GA | | 57-0 | 28-21-22 | | D41718P | 16 | | | D40332J | 20 | | | 001-099 |
| 0085 | 20 | | GA | | 59-0 | 28-21-22 | | D41718P | 16 | | | D40332J | 20 | | | 115-199 |
| 0086 | 22 | | GA | | 24-0 | 74-31-21 | | D41730P | 4 | | | D41616P | 8 | | | 001-099 |
| 0086 | 22 | | GA | | 25-0 | 74-31-21 | | D41730P | 4 | | | D41616P | 8 | | | 115-199 |
| 0087 | 22 | | GA | | 63-0 | 27-18-11 | | D41720P | 15 | | | D40930P | 8 | | | 001-099 |
| 0087 | 22 | | GA | | 64-0 | 27-18-11 | | D41720P | 15 | | | D40930J | 8 | | | 115-199 |
| 0088 | 22 | | GA | | 10-0 | 74-31-21 | | D41730P | 2 | | | D41658P | 10 | | | 001-099 |
| 0088 | 22 | | GA | | 25-0 | 74-31-21 | | D41616P | 10 | | | D41658P | 10 | | | 115-199 |
| 0089 | 20 | | GA | | 16-0 | 28-21-11 | | D41616P | 39 | | | SM00006 | | 9 | | 001-099 |
| 0090 | 22 | | GA | | 27-0 | 32-09-12 | | D41616P | 35 | | | D42060P | 26 | | | 001-002 |
| 0090 | 22 | | GA | | 27-0 | 32-09-12 | | D41616P | 35 | | | D42060P | 24 | | | 003-099, 115-199 |
| 0091 | 22 | | GA | | 27-0 | 32-09-12 | | D41616P | 36 | | | D42060P | 25 | | | ALL |
| 0092 | 22 | | GA | | 27-0 | 32-09-12 | | D41616P | 37 | | | D42060P | 24 | | | 001-002 |
| 0092 | 22 | | GA | | 27-0 | 32-09-12 | | D41616P | 37 | | | D42060P | 26 | | | 003-099, 115-199 |
| 0093 | 22 | | GA | | 27-0 | 32-09-12 | | D41616P | 2 | | | D42060P | 30 | | | ALL |
| 0097 | 22 | | GA | | 74-0 | 29-21-32 | | D41616P | 31 | | | D40358J | 14 | | | 001-099 |
| 0097 | 22 | | GA | | 73-0 | 29-21-32 | | D41616P | 31 | | | D40358J | 14 | | | 115-199 |
| 0098 | 22 | | GA | | 74-0 | 29-21-32 | | D41616P | 30 | | | D40358J | 13 | | | 001-099 |
| 0098 | 22 | | GA | | 73-0 | 29-21-32 | | D41616P | 30 | | | D40358J | 13 | | | 115-199 |
| 0099 | 20 | | GA | | 74-0 | 29-21-32 | | D42062P | 5 | | | D40358J | 12 | | | ALL |
| 0100 | 20 | | GA | | 74-0 | 29-21-32 | | D42062P | 3 | | | D40358J | 6 | | | ALL |
| 0101 | 20 | | GA | | 54-0 | SPARE | | D42060P | 2 | | | D40334J | 8 | | | 001-099 |
| 0103 | 22 | | GA | | 54-0 | SPARE | | D42060P | 9 | | | D40334J | 3 | | | 001-099 |
| 0103 | 22 | | GA | | 29-0 | SPARE | | D42060P | 29 | | | D41658P | 11 | | | 115-199 |
| 0104 | 22 | | GA | | 62-0 | SPARE | | D41658P | 12 | | | D40930P | 26 | | | 001-099 |
| 0104 | 22 | | GA | | 62-0 | SPARE | | D41658P | 12 | | | D40930J | 24 | | | 115-199 |
| 0105 | 22 | | GA | | 63-0 | SPARE | | D41720P | 16 | | | D40930P | 24 | | | 001-099 |
| 0105 | 22 | | GA | | 64-0 | SPARE | | D41720P | 16 | | | D40930J | 26 | | | 115-199 |
| 0106 | 22 | | GA | | 73-0 | SPARE | | D42060P | 11 | | | D40930P | 34 | | | 001-099 |
| 0106 | 22 | | GA | | 66-0 | SPARE | | D41730P | 11 | | | D40360J | 19 | | | 115-199 |
| 0107 | 20 | | GA | | 74-0 | SPARE | | D42062P | | CAP | Y | D40358J | 5 | | | ALL |
| 0108 | 20 | | GA | | 77-0 | SPARE | | D41718P | 32 | | | D40930P | 35 | | | 001-099 |
| 0108 | 20 | | GA | | 59-0 | SPARE | | D41718P | 32 | | | D40334J | 48 | | | 115-199 |
| 0109 | 20 | | GA | | 57-0 | SPARE | | D41718P | 33 | | | D40334J | 49 | | | 001-099 |
| 0109 | 20 | | GA | | 59-0 | SPARE | | D41718P | 33 | | | D40334J | 49 | | | 115-199 |
| 0110 | 20 | | GA | | 57-0 | SPARE | | D41718P | 34 | | | D40334J | 50 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4216 | 286N4216 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | |
| 0110 | 20 | | GA | | 59-0 | SPARE | D41718P | 34 | | | D40334J | 50 | | | 115-199 |
| 0111 | 20 | | GA | | 57-0 | SPARE | D41718P | 35 | | | D40332J | 18 | | | 001-099 |
| 0111 | 20 | | GA | | 59-0 | SPARE | D41718P | 35 | | | D40332J | 18 | | | 115-199 |
| 0112 | 20 | | GA | | 57-0 | SPARE | D41718P | 36 | | | D40332J | 19 | | | 001-099 |
| 0112 | 20 | | GA | | 59-0 | SPARE | D41718P | 36 | | | D40332J | 19 | | | 115-199 |
| 0113 | 22 | | GA | | 20-0 | 29-22-11 | D41616P | 38 | | | D41720P | 17 | | | 001-099 |
| 0113 | 22 | | GA | | 21-0 | 29-22-11 | D41616P | 38 | | | D41720P | 17 | | | 115-199 |
| 0114 | 20 | | GA | | 10-0 | 29-35-11 | D41720P | 18 | | | SM00002 | | 9 | | 001-099 |
| 0114 | 20 | | GA | | 67-0 | 29-35-11 | D41720P | 18 | | | D40360J | 20 | | | 115-199 |
| 0115 | 20 | | GA | | 72-0 | 29-35-11 | D41720P | 19 | | | D40360J | 21 | | | 001-099 |
| 0115 | 20 | | GA | | 67-0 | 29-35-11 | D41720P | 19 | | | D40360J | 21 | | | 115-199 |
| 0116 | 22 | | GA | | 32-0 | 27-51-21 | D41718P | 29 | | | D41658P | 8 | | | 001-099 |
| 0116 | 22 | | GA | | 33-0 | 27-51-21 | D41718P | 29 | | | D41658P | 8 | | | 115-199 |
| 0117 | 22 | | GA | | 61-0 | 27-23-11 | D40360J | 3 | | | SM00001 | | 9 | | 001-099 |
| 0117 | 22 | | GA | | 62-0 | SPARE | D40930J | 28 | | | D41658P | 9 | | | 115-199 |
| 0118 | 22 | | GA | | 25-0 | 76-11-21 | D41616P | 7 | | | D41730P | 3 | | | 001-099 |
| 0119 | 20 | | GA | | 69-0 | SPARE | D42062P | | CAP | Y | D40930P | 28 | | | 001-099 |
| 0120 | 20 | | GA | | 15-0 | 29-35-11 | D42062P | 12 | | | SM00002 | | 9 | | 001-099 |
| 0121 | 20 | | GA | | 61-0 | 29-35-11 | D40360J | 20 | | | SM00002 | | 9 | | 001-099 |
| 0122 | 20 | | GA | | 23-0 | 28-21-11 | D41718P | 4 | | | SM00006 | | 9 | | 001-099 |
| 0123 | 20 | | GA | | 36-0 | 28-21-11 | SM00006 | | | 9 | D40334J | 6 | | | 001-099 |
| 1025 | 22 | | GT | BC | 63-0 | 27-18-11 | D41720P | 10 | | | D40930P | 36 | | | 001-099 |
| 1025 | 22 | | GT | BC | 64-0 | 27-18-11 | D41720P | 10 | | | D40930J | 36 | | | 115-199 |
| 1025Z | | | | BC | 0-0 | 27-18-11 | D41720P | 11 | | | D40930P | S/R | | | 001-099 |
| 1025Z | | | | BC | 0-0 | 27-18-11 | D41720P | 11 | | | D40930J | S/R | | | 115-199 |
| 2001B | 22 | | GB | AA | 78-0 | 32-61-13 | D42060P | 14 | | | D40358J | 10 | | | 001-099 |
| 2001B | 22 | | GB | AA | 76-0 | 32-61-13 | D42060P | 14 | | | D40358J | 10 | | | 115-199 |
| 2001R | 22 | | GB | AA | 0-0 | 32-61-13 | D42060P | 15 | | | D40358J | 11 | | | ALL |
| 2002B | 22 | | GB | AB | 77-0 | 32-61-13 | D42060P | 16 | | | D40358J | 4 | | | ALL |
| 2002R | 22 | | GB | AB | 0-0 | 32-61-13 | D42060P | 17 | | | D40358J | 9 | | | ALL |
| 2003B | 24 | | GL | AC | 69-0 | 32-61-22 | D42060P | 18 | | | SM00003 | | 9 | | 001-099 |
| 2003B | 24 | | GL | AC | 67-0 | 32-61-22 | D42060P | 18 | | | SM00003 | | 9 | | 115-199 |
| 2003R | 24 | | GL | AC | 0-0 | 32-61-22 | D42060P | 19 | | | SM00004 | | 9 | | ALL |
| 2004B | 20 | | GB | AD | 56-0 | 28-21-22 | D41614P | 14 | | | D40334J | 23 | | | 115-199 |
| 2004R | 20 | | GB | AD | 0-0 | 28-21-22 | D41614P | 15 | | | D40334J | 22 | | | 115-199 |
| 2005B | 20 | | GB | AE | 56-0 | SPARE | D41614P | 16 | | | D40334J | 25 | | | 115-199 |
| 2005R | 20 | | GB | AE | 0-0 | SPARE | D41614P | 17 | | | D40334J | 24 | | | 115-199 |
| 2006B | 20 | | GB | AF | 56-0 | SPARE | D41614P | | CAP | Y | D40334J | | CAP | Y | 115-199 |
| 2006R | 20 | | GB | AF | 0-0 | SPARE | D41614P | | CAP | Y | D40334J | | CAP | Y | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4216 | 286N4216 | | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | |
| 2007B | 20 | GB | AG | | 56-0 | SPARE | D41614P | 8 | | | | D40334J | 13 | | | 115-199 |
| 2007R | 20 | GB | AG | | 0-0 | SPARE | D41614P | 9 | | | | D40334J | CAP | Y | | 115-199 |
| 2008B | 20 | GB | AH | | 56-0 | SPARE | D41614P | CAP | Y | | | D40334J | CAP | Y | | 115-199 |
| 2008R | 20 | GB | AH | | 0-0 | SPARE | D41614P | CAP | Y | | | D40334J | CAP | Y | | 115-199 |
| 2009B | 20 | GB | AI | | 56-0 | SPARE | D41614P | CAP | Y | | | D40334J | CAP | Y | | 115-199 |
| 2009R | 20 | GB | AI | | 0-0 | SPARE | D41614P | 13 | | | | D40334J | 16 | | | 115-199 |
| 2010B | 22 | GB | AJ | | 62-0 | 27-51-61 | D41658P | 1 | | | | D40930P | 2 | | | 001-099 |
| 2010B | 22 | GB | AJ | | 62-0 | 27-51-61 | D41658P | 1 | | | | D40930J | 2 | | | 115-199 |
| 2010R | 22 | GB | AJ | | 0-0 | 27-51-61 | D41658P | 2 | | | | D40930P | 1 | | | 001-099 |
| 2010R | 22 | GB | AJ | | 0-0 | 27-51-61 | D41658P | 2 | | | | D40930J | 1 | | | 115-199 |
| 2012B | 22 | GB | AL | | 63-0 | 27-18-11 | D41720P | 13 | | | | D40930P | 9 | | | 001-099 |
| 2012B | 22 | GB | AL | | 64-0 | 27-18-11 | D41720P | 13 | | | | D40930J | 9 | | | 115-199 |
| 2012R | 22 | GB | AL | | 0-0 | 27-18-11 | D41720P | 14 | | | | D40930P | 10 | | | 001-099 |
| 2012R | 22 | GB | AL | | 0-0 | 27-18-11 | D41720P | 14 | | | | D40930J | 10 | | | 115-199 |
| 2013B | 20 | GB | AM | | 69-0 | 32-09-12 | D41614P | 53 | | | | SP00317 | | 9 | | 001-099 |
| 2013B | 20 | GB | AM | | 71-0 | 32-09-12 | D41614P | 53 | | | | SP00317 | | 9 | | 115-199 |
| 2013R | 20 | GB | AM | | 0-0 | 32-09-12 | D41614P | 54 | | | | SP00319 | | 9 | | ALL |
| 2014B | 22 | GB | AN | | 75-0 | 28-41-31 | D41614P | 19 | | | | D40930J | 4 | | | 115-199 |
| 2014R | 22 | GB | AN | | 0-0 | 28-41-31 | D41614P | 18 | | | | D40930J | 3 | | | 115-199 |
| 2015B | 22 | GB | AO | | 75-0 | 28-41-31 | D41614P | 21 | | | | D40930J | 6 | | | 115-199 |
| 2015R | 22 | GB | AO | | 0-0 | 28-41-31 | D41614P | 20 | | | | D40930J | 5 | | | 115-199 |
| 2016B | 22 | GB | AP | | 75-0 | 28-41-41 | D41614P | 23 | | | | D40930J | 13 | | | 115-199 |
| 2016R | 22 | GB | AP | | 0-0 | 28-41-41 | D41614P | 22 | | | | D40930J | 12 | | | 115-199 |
| 2017B | 22 | GB | AQ | | 75-0 | 28-41-41 | D41614P | 25 | | | | D40930J | 15 | | | 115-199 |
| 2017R | 22 | GB | AQ | | 0-0 | 28-41-41 | D41614P | 24 | | | | D40930J | 14 | | | 115-199 |
| 2018B | 18 | GB | AR | | 73-0 | 28-43-11 | D41614P | 26 | 18 | | | D40930P | 25 | 18 | | 001-099 |
| 2018B | 18 | GB | AR | | 75-0 | 28-43-11 | D41614P | 26 | 18 | | | D40930J | 25 | 18 | | 115-199 |
| 2018R | 18 | GB | AR | | 0-0 | 28-43-11 | D41614P | 27 | 18 | | | D40930P | 27 | 18 | | 001-099 |
| 2018R | 18 | GB | AR | | 0-0 | 28-43-11 | D41614P | 27 | 18 | | | D40930J | 27 | 18 | | 115-199 |
| 2019B | 20 | GB | AT | | 54-0 | 28-21-22 | D41614P | 32 | | | | D40334J | 38 | | | 001-099 |
| 2019R | 20 | GB | AT | | 0-0 | 28-21-22 | D41614P | 50 | | | | D40334J | 42 | | | 001-099 |
| 2501B | 20 | GU | DA | | 54-0 | 23-41-12 | D42060P | 20 | | | | D40334J | 2 | | | 001-099 |
| 2501R | 20 | GU | DA | | 0-0 | 23-41-12 | D42060P | 21 | | | | D40334J | 1 | | | 001-099 |
| 2501Z | | | DA | | 0-0 | 23-41-12 | D42060P | 23 | | | | D40334J | 4 | | | 001-099 |
| 2506B | 20 | GU | AF | | 54-0 | 28-41-11 | D41614P | 6 | | | | D40334J | 11 | | | 001-099 |
| 2506B | 20 | GU | FA | | 55-0 | 28-41-11 | D41614P | 6 | | | | D40334J | 11 | | | 115-199 |
| 2506R | 20 | GU | AF | | 0-0 | 28-41-11 | D41614P | 7 | | | | D40334J | 10 | | | 001-099 |
| 2506R | 20 | GU | FA | | 0-0 | 28-41-11 | D41614P | 7 | | | | D40334J | 10 | | | 115-199 |
| 2506Z | | | AF | | 0-0 | 28-41-11 | D41614P | 5 | | | | D40334J | 12 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4216 | 286N4216 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | |
| 2506Z | | | | FA | 0-0 | 28-41-11 | D41614P | | 5 | | D40334J | 12 | | | 115-199 |
| 2508B | 20 | GU | | AH | 54-0 | 28-41-11 | D41614P | | 10 | | D40334J | 19 | | | 001-099 |
| 2508B | 20 | GU | | HA | 55-0 | 28-41-11 | D41614P | | 10 | | D40334J | 19 | | | 115-199 |
| 2508R | 20 | GU | | AH | 0-0 | 28-41-11 | D41614P | | 11 | | D40334J | 18 | | | 001-099 |
| 2508R | 20 | GU | | HA | 0-0 | 28-41-11 | D41614P | | 11 | | D40334J | 18 | | | 115-199 |
| 2508Z | | | | AH | 0-0 | 28-41-11 | D41614P | | 12 | | D40334J | 17 | | | 001-099 |
| 2508Z | | | | HA | 0-0 | 28-41-11 | D41614P | | 12 | | D40334J | 17 | | | 115-199 |
| 2512B | 20 | GF | | BA | 9-0 | 32-61-22 | D40440J | | 2 | | SM00003 | | 9 | | 001-099 |
| 2512B | 20 | GF | | BA | 8-0 | 32-61-22 | D40440J | | 2 | | SM00003 | | 9 | | 115-199 |
| 2512R | 20 | GF | | BA | 0-0 | 32-61-22 | D40440J | | 1 | | SM00004 | | 9 | | ALL |
| 2512Z | | | | BA | 0-0 | 32-61-22 | D40440J | DED | | | SM00003 | | 9 | | ALL |
| 3001B | 16 | GC | | CA | 74-0 | 28-22-11 | D42062P | | 4 | | D40358J | 3 | | | ALL |
| 3001R | 16 | GC | | CA | 0-0 | 28-22-11 | D42062P | | 2 | | D40358J | 2 | | | ALL |
| 3001Y | 16 | GC | | CA | 0-0 | 28-22-11 | D42062P | | 1 | | D40358J | 1 | | | ALL |
| 3002B | 18 | GC | | AK | 69-0 | 28-22-11 | D42062P | | 10 | | SP05018 | | 9 | | 001-099 |
| 3002B | 18 | GC | | BB | 70-0 | 28-22-11 | D42062P | | 10 | | SP05018 | | 9 | | 115-199 |
| 3002R | 18 | GC | | AK | 0-0 | 28-22-11 | D42062P | | 8 | | SP05014 | | 9 | | 001-099 |
| 3002R | 18 | GC | | BB | 0-0 | 28-22-11 | D42062P | | 8 | | SP05014 | | 9 | | 115-199 |
| 3002Y | 18 | GC | | AK | 0-0 | 28-22-11 | D42062P | | 9 | | SP05016 | | 9 | | 001-099 |
| 3002Y | 18 | GC | | BB | 0-0 | 28-22-11 | D42062P | | 9 | | SP05016 | | 9 | | 115-199 |
| 3003B | 22 | GC | | CC | 54-0 | 28-21-22 | D41614P | | 41 | | D40332J | 12 | | | 001-099 |
| 3003B | 20 | GC | | CC | 56-0 | 28-21-22 | D41614P | | 41 | | D40332J | 12 | | | 115-199 |
| 3003R | 22 | GC | | CC | 0-0 | 28-21-22 | D41614P | | 42 | | D40332J | 13 | | | 001-099 |
| 3003R | 20 | GC | | CC | 0-0 | 28-21-22 | D41614P | | 42 | | D40332J | 13 | | | 115-199 |
| 3003Y | 22 | GC | | CC | 0-0 | 28-21-22 | D41614P | | 43 | | D40332J | 14 | | | 001-099 |
| 3003Y | 20 | GC | | CC | 0-0 | 28-21-22 | D41614P | | 43 | | D40332J | 14 | | | 115-199 |
| 3004B | 20 | GC | | AS | 54-0 | 28-21-22 | D41614P | | 31 | | D40334J | 41 | | | 001-099 |
| 3004R | 20 | GC | | AS | 0-0 | 28-21-22 | D41614P | | 30 | | D40334J | 39 | | | 001-099 |
| 3004Y | 20 | GC | | AS | 0-0 | 28-21-22 | D41614P | | 33 | | D40334J | 40 | | | 001-099 |
| 3501B | 20 | GV | | DA | 53-0 | 23-41-12 | D42060P | | 20 | | D40334J | 2 | | | 115-199 |
| 3501R | 20 | GV | | DA | 0-0 | 23-41-12 | D42060P | | 21 | | D40334J | 1 | | | 115-199 |
| 3501Y | 20 | GV | | DA | 0-0 | 23-41-12 | D42060P | | 22 | | D40334J | 3 | | | 115-199 |
| 3501Z | | | | DA | 0-0 | 23-41-12 | D42060P | | 23 | | D40334J | 4 | | | 115-199 |
| 4001B | 22 | GD | | EA | 62-0 | 27-51-61 | D41658P | | 3 | | D40930P | 17 | | | 001-099 |
| 4001B | 22 | GD | | EA | 62-0 | 27-51-61 | D41658P | | 3 | | D40930J | 17 | | | 115-199 |
| 4001G | 22 | GD | | EA | 0-0 | 27-51-61 | D41658P | | 4 | | D40930P | 19 | | | 001-099 |
| 4001G | 22 | GD | | EA | 0-0 | 27-51-61 | D41658P | | 4 | | D40930J | 19 | | | 115-199 |
| 4001R | 22 | GD | | EA | 0-0 | 27-51-61 | D41658P | | 5 | | D40930P | 16 | | | 001-099 |
| 4001R | 22 | GD | | EA | 0-0 | 27-51-61 | D41658P | | 5 | | D40930J | 16 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description FT-IN | Diagram | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4216 | 286N4216 | | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2A (continued) | | | | | | | | | | | | |
| 4001Y | 22 | GD | EA | | 0-0 | 27-51-61 | D41658P | 6 | | | | D40930P | 18 | | | 001-099 | |
| 4001Y | 22 | GD | EA | | 0-0 | 27-51-61 | D41658P | 6 | | | | D40930J | 18 | | | 115-199 | |
| 4002B | 22 | GD | EB | | 56-0 | 28-21-22 | D41614P | 30 | | | | D40334J | 39 | | | 115-199 | |
| 4002G | 22 | GD | EB | | 0-0 | 28-21-22 | D41614P | 31 | | | | D40334J | 41 | | | 115-199 | |
| 4002R | 22 | GD | EB | | 0-0 | SPARE | D41614P | 32 | | | | D40334J | 38 | | | 115-199 | |
| 4002Y | 22 | GD | EB | | 0-0 | 28-21-22 | D41614P | 33 | | | | D40334J | 40 | | | 115-199 | |
| 4003B | 22 | GD | EC | | 54-0 | 28-21-22 | D41614P | 55 | | | | D40332J | 23 | | | 001-099 | |
| 4003B | 20 | GD | EC | | 56-0 | 28-21-22 | D41614P | 55 | | | | D40332J | 23 | | | 115-199 | |
| 4003G | 22 | GD | EC | | 0-0 | 28-21-22 | D41614P | 38 | | | | D40332J | 10 | | | 001-099 | |
| 4003G | 20 | GD | EC | | 0-0 | 28-21-22 | D41614P | 38 | | | | D40332J | 10 | | | 115-199 | |
| 4003R | 22 | GD | EC | | 0-0 | 28-21-22 | D41614P | 39 | | | | D40332J | 11 | | | 001-099 | |
| 4003R | 20 | GD | EC | | 0-0 | 28-21-22 | D41614P | 39 | | | | D40332J | 11 | | | 115-199 | |
| 4003Y | 22 | GD | EC | | 0-0 | 28-21-22 | D41614P | 40 | | | | D40332J | 22 | | | 001-099 | |
| 4003Y | 20 | GD | EC | | 0-0 | 28-21-22 | D41614P | 40 | | | | D40332J | 21 | | | 115-199 | |
| YAAA | | | | | 0-0 | 28-41-11 | D40334J | S/R | | | | GD03077 | ST.. | E | * | 001-099 | |
| YAAA | | | | | 0-0 | 28-21-22 | GD03077 | ST.. | E | *1 | | D40332J | S/R | | | 115-199 | |
| YAAB | | | | | 0-0 | 28-21-22 | D40332J | S/R | | | | GD03077 | ST.. | E | * | 001-099 | |
| YAAB | | | | | 0-0 | 28-41-11 | GD03077 | ST.. | E | *1 | | D40334J | S/R | | | 115-199 | |
| YAAF | | | | | 0-0 | 28-42-11 | GD02540 | ST.. | E | * | | SP05014 | DED | | | 115-199 | |
| YAAG | | | | | 0-0 | 27-51-61 | D40930P | S/R | | | | GD02540 | ST.. | E | * | 001-099 | |
| YAAH | | | | | 0-0 | 32-61-22 | D40440J | S/R | | | | GD02540 | ST.. | E | * | 001-099 | |
| YAAH | | | | | 0-0 | 32-61-12 | D40440J | S/R | | | | GD02540 | ST.. | E | * | 115-199 | |
| W4218 | 286N4218 | | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2B | | | | | | | | | | | | |
| 0001 | 22 | GA | | | 46-0 | 27-38-11 | D41632P | 14 | | | | D41180J | 1 | | | ALL | |
| 0002 | 22 | GA | | | 41-0 | 27-81-31 | D41828P | 7 | | | | D41198J | 22 | | | ALL | |
| 0003 | 20 | GA | | | 50-0 | 33-42-12 | D41728P | 6 | | | | D40402J | 3 | | | ALL | |
| 0004 | 20 | GA | | | 50-0 | 33-42-12 | D41728P | 7 | | | | D40402J | 4 | | | ALL | |
| 0006 | 20 | GA | | | 56-0 | 33-45-11 | D41620P | 20 | | | | D41180J | 8 | | | 001-099 | |
| 0006 | 20 | GA | | | 59-0 | 33-45-11 | D41620P | 20 | | | | D41180J | 8 | | | 115-199 | |
| 0007 | 22 | GA | | | 46-0 | 27-23-11 | D41180J | 4 | | | | D41632P | 7 | | | ALL | |
| 0008 | 22 | GA | | | 46-0 | 27-23-11 | D41180J | 5 | | | | D41632P | 8 | | | ALL | |
| 0009 | 24 | GK | | | 28-0 | 29-11-12 | D41620P | 24 | | | | D41632P | 9 | | | 115-199 | |
| 0010 | 22 | GA | | | 50-0 | SPARE | D40402J | 13 | | | | D41728P | 12 | | | 001-099 | |
| 0010 | 24 | GK | | | 28-0 | 29-11-12 | D41620P | 25 | | | | D41632P | 10 | | | 115-199 | |
| 0011 | 22 | GA | | | 43-0 | SPARE | D40402J | 11 | | | | D41632P | 11 | | | 001-099 | |
| 0011 | 24 | GK | | | 28-0 | SPARE | D41620P | 26 | | | | D41632P | 11 | | | 115-199 | |
| 0012 | 22 | GA | | | 31-0 | SPARE | D41620P | 27 | | | | D41728P | 12 | | | 115-199 | |
| 0013 | 22 | GA | | | 31-0 | SPARE | D41620P | 28 | | | | D41728P | 13 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|---------|-------|------|-------------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | |
| W4218 | 286N4218 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2B (continued) | | | | | | | | | | |
| 001TI | | | | XA | 0-0 | 28-41-31 | D42222P | = C1 | | | D02818 | = C1 | | 115-199 |
| 001TO | | | | XA | 0-0 | 28-41-31 | D42222P | 2 | | | GD02145 | ST.. | GW | 115-199 |
| 001TX | 18 | TK | | XA | 82-0 | 28-41-31 | D42222P | 1 | | | D02818 | 1 | VN | 115-199 |
| 002TI | | | | XB | 0-0 | 28-41-41 | D42226P | = C1 | | | D02812 | = C1 | | 115-199 |
| 002TO | | | | XB | 0-0 | 28-41-41 | D42226P | 2 | | | GD00336 | ST.. | E | 115-199 |
| 002TX | 18 | TK | | XB | 57-0 | 28-41-41 | D42226P | 1 | | | D02812 | 1 | VN | 115-199 |
| 0032 | 20 | GA | | | 50-0 | 33-43-12 | D41728P | 8 | | | D40402J | 18 | | ALL |
| 0033 | 20 | GA | | | 50-0 | SPARE | D41728P | 9 | | | D40402J | 2 | | ALL |
| 0034 | 20 | GA | | | 50-0 | 33-44-21 | D41728P | 10 | | | D40402J | 5 | | ALL |
| 0036 | 20 | GA | | | 31-0 | 33-41-11 | D41728P | 11 | | | L00069 | 115V | E | ALL |
| 0037 | 14 | GA | | | 3-0 | 33-41-11 | L00069 | RTN | E | | GD00593 | AC.. | E | ALL |
| 0038 | 14 | GA | | | 3-0 | 33-41-11 | L00069 | GND | E | | GD01666 | ST.. | E | ALL |
| 0039 | 22 | GA | | | 27-0 | 32-09-11 | D41620P | 15 | | | D41632P | 3 | | 001-099 |
| 0039 | 22 | GA | | | 29-0 | 32-09-11 | D41620P | 15 | | | D41632P | 3 | | 115-199 |
| 0040 | 22 | GA | | | 27-0 | 32-09-11 | D41620P | 21 | | | D41632P | 4 | | 001-099 |
| 0040 | 22 | GA | | | 28-0 | 32-09-11 | D41620P | 35 | | | D41632P | 4 | | 115-199 |
| 0041 | 22 | GA | | | 44-0 | 27-23-21 | D41828P | 8 | | | D41180J | 7 | | 001-099 |
| 0041 | 22 | GA | | | 43-0 | 27-23-21 | D41828P | 8 | | | D41180J | 7 | | 115-199 |
| 0042 | 22 | GA | | | 44-0 | 27-23-21 | D41828P | 9 | | | D41180J | 6 | | 001-099 |
| 0042 | 22 | GA | | | 43-0 | 27-23-21 | D41828P | 9 | | | D41180J | 6 | | 115-199 |
| 0043 | 20 | GA | | | 57-0 | SPARE | D41620P | 21 | | | D40402J | 19 | | 115-199 |
| 0044 | 20 | GA | | | 57-0 | SPARE | D41620P | 23 | | | D40402J | 20 | | 115-199 |
| 0045 | 22 | GA | | | 43-0 | SPARE | D41828P | 10 | | | D41180J | 9 | | 115-199 |
| 0321 | 22 | GA | | | 28-0 | SPARE | D41620P | 33 | | | D41632P | 1 | | 115-199 |
| 0322 | 22 | GA | | | 28-0 | SPARE | D41620P | 34 | | | D41632P | 2 | | 115-199 |
| 0358 | 24 | GK | | | 23-0 | SPARE | D41728P | 32 | | | D41632P | 24 | | 001-099 |
| 0359 | 24 | GK | | | 28-0 | SPARE | D41728P | 33 | | | D41620P | 31 | | 001-099 |
| 1025 | 22 | GT | BC | | 46-0 | 27-38-11 | D41632P | 6 | | | D41180J | 10 | | 001-099 |
| 1025 | 22 | GT | BC | | 46-0 | 27-38-11 | D41180J | 10 | | | D41632P | 6 | | 115-199 |
| 1025Z | | | | BC | 0-0 | 27-38-11 | D41632P | 5 | | | D41180J | 11 | | ALL |
| 2001B | 22 | GB | AG | | 46-0 | 27-38-11 | D41632P | 15 | | | D41180J | 3 | | ALL |
| 2001R | 22 | GB | AG | | 0-0 | 27-38-11 | D41632P | 16 | | | D41180J | 2 | | ALL |
| 2002B | 22 | GB | AH | | 41-0 | 27-51-61 | D41828P | 6 | | | D41198J | 17 | | ALL |
| 2002R | 22 | GB | AH | | 0-0 | 27-51-61 | D41828P | 5 | | | D41198J | 16 | | ALL |
| 2006B | 22 | GB | AF | | 31-0 | SPARE | D41620P | CAP | Y | | D41728P | CAP | Y | 115-199 |
| 2006R | 22 | GB | AF | | 0-0 | SPARE | D41620P | CAP | Y | | D41728P | CAP | Y | 115-199 |
| 3002B | 24 | GM | AB | | 28-0 | 28-41-14 | D41620P | 18 | | | D41728P | 40 | | 001-099 |
| 3002B | 24 | GM | FA | | 30-0 | 28-41-14 | D41620P | 18 | | | D41728P | 3 | | 115-199 |
| 3002R | 24 | GM | AB | | 0-0 | 28-41-14 | D41620P | 19 | | | D41728P | 42 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4218 | 286N4218 | | | E/E BAY TO RIGHT WING/BODY AND BODY/SPAR INSTALLATIONS - R2B (continued) | | | | | | | | | | | | |
| 3002R | 24 | GM | FA | | 0-0 | 28-41-14 | D41620P | 19 | | | D41728P | 4 | | | 115-199 | |
| 3002Y | 24 | GM | AB | | 0-0 | 28-41-14 | D41620P | 30 | | | D41728P | 41 | | | 001-099 | |
| 3002Y | 24 | GM | FA | | 0-0 | 28-41-14 | D41620P | 30 | | | D41728P | 5 | | | 115-199 | |
| 4001B | 22 | GD | EA | | 41-0 | 27-51-61 | D41828P | 1 | | | D41198J | 18 | | | ALL | |
| 4001G | 22 | GD | EA | | 0-0 | 27-51-61 | D41828P | 2 | | | D41198J | 21 | | | ALL | |
| 4001R | 22 | GD | EA | | 0-0 | 27-51-61 | D41828P | 3 | | | D41198J | 19 | | | ALL | |
| 4001Y | 22 | GD | EA | | 0-0 | 27-51-61 | D41828P | 4 | | | D41198J | 20 | | | ALL | |
| 4501AA | 20 | 4K | BA | | 57-0 | SPARE | D41620P | 38 | | | D41198J | 14 | | | 115-199 | |
| 4501RB | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 5 | | | D41198J | 5 | | | 115-199 | |
| 4501RG | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 4 | | | D41198J | 4 | | | 115-199 | |
| 4501RK | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 3 | | | D41198J | 3 | | | 115-199 | |
| 4501RV | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 7 | | | D41198J | 7 | | | 115-199 | |
| 4501RY | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 2 | | | D41198J | 2 | | | 115-199 | |
| 4501W | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 1 | | | D41198J | 1 | | | 115-199 | |
| 4501WB | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 37 | | | D41198J | 13 | | | 115-199 | |
| 4501WG | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 36 | | | D41198J | 12 | | | 115-199 | |
| 4501WK | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 6 | | | D41198J | 6 | | | 115-199 | |
| 4501WN | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 8 | | | D41198J | 8 | | | 115-199 | |
| 4501WO | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 11 | | | D41198J | 11 | | | 115-199 | |
| 4501WR | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 9 | | | D41198J | 9 | | | 115-199 | |
| 4501WV | 20 | 4K | BA | | 0-0 | SPARE | D41620P | 39 | | | D41198J | 15 | | | 115-199 | |
| 4501WY | 20 | 4K | BA | | 0-0 | 28-41-31 | D41620P | 10 | | | D41198J | 10 | | | 115-199 | |
| 4501Z | | | BA | | 0-0 | 28-41-31 | D41620P | 22 | | | D41198J | S/R | | | 115-199 | |
| 4502B | 20 | 4L | BB | | 61-0 | 28-41-41 | D41620P | 17 | | | D02808 | 1 | | | 115-199 | |
| 4502G | 20 | 4L | BB | | 0-0 | 28-41-41 | D41620P | 13 | | | D02808 | 3 | | | 115-199 | |
| 4502K | 20 | 4L | BB | | 0-0 | 28-41-41 | D41620P | 16 | | | D02808 | 5 | | | 115-199 | |
| 4502R | 20 | 4L | BB | | 0-0 | 28-41-41 | D41620P | 12 | | | D02808 | 2 | | | 115-199 | |
| 4502Y | 20 | 4L | BB | | 0-0 | 28-41-41 | D41620P | 14 | | | D02808 | 4 | | | 115-199 | |
| 4502Z | | | BB | | 0-0 | 28-41-41 | D41620P | 29 | | | GD00334 | ST.. | E | | 115-199 | |
| FRZA | | | | | 0-6 | 28-41-41 | D02812 | | | ZA | GD00336 | ST.. | E | | 115-199 | |
| FRZB | | | | | 0-6 | 28-41-41 | D02808 | | | ZB | GD00334 | ST.. | E | | 115-199 | |
| YAAA | | | | | 0-0 | 28-41-41 | GD01831 | ST.. | E | *1 | D02812 | | | ZA | 115-199 | |
| YAAB | | | | | 0-0 | 28-41-41 | GD01831 | ST.. | E | *1 | D02808 | | | ZB | 115-199 | |
| YAAC | | | | | 0-0 | 33-42-12 | D40402J | S/R | | | GD01831 | ST.. | E | | 001-099 | |
| YAAC | | | | | 0-0 | 33-42-12 | GD01831 | ST.. | E | *1 | D40402J | S/R | | | 115-199 | |
| YAAD | | | | | 0-0 | 27-51-61 | D41198J | S/R | | | GD01831 | ST.. | E | | 001-099 | |
| YAAD | | | | | 0-0 | 28-41-31 | GD01831 | ST.. | E | *2 | D41198J | S/R | | | 115-199 | |
| YAAE | | | | | 0-0 | 28-41-31 | GD01831 | ST.. | E | *2 | GD03086 | ST.. | E | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4210

Page 21 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4220 | 286N4220 | | | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC | | | | | | | | | | | |
| 0001 | 22 | | GA | | 44-0 | 30-21-11 | D41736P | | | | D40032J | 11 | | | 001-099 |
| 0001 | 22 | | GA | | 43-0 | 30-21-11 | D40032J | | | 11 | D41736P | 1 | | | 115-199 |
| 0002 | 22 | | GA | | 44-0 | 30-21-11 | D41736P | | | 7 | D40032J | 12 | | | 001-099 |
| 0002 | 22 | | GA | | 43-0 | 30-21-11 | D40032J | | | 12 | D41736P | 7 | | | 115-199 |
| 0003 | 22 | | GA | | 34-0 | 29-22-11 | D42002P | | | 11 | D42094P | 5 | | | 001-099 |
| 0003 | 22 | | GA | | 48-0 | 30-21-11 | D40032J | | | 13 | D41994P | 5 | | | 115-199 |
| 0004 | 22 | | GA | | 52-0 | 26-18-21 | D40032J | | | 8 | D42002P | 1 | | | 001-099 |
| 0004 | 20 | | GA | | 53-0 | 26-18-21 | D40032J | | | 8 | D42002P | 1 | | | 115-199 |
| 0005 | 22 | | GA | | 52-0 | 26-18-21 | D40032J | | | 9 | D42002P | 2 | | | 001-099 |
| 0005 | 20 | | GA | | 53-0 | 26-18-21 | D40032J | | | 9 | D42002P | 2 | | | 115-199 |
| 0006 | 22 | | GA | | 23-0 | 26-18-21 | D41736P | | | 17 | D42002P | 3 | | | ALL |
| 0007 | 20 | | GA | | 49-0 | 74-31-21 | D40032J | | | 18 | D41994P | 34 | | | 001-099 |
| 0007 | 20 | | GA | | 48-0 | 74-31-21 | D40032J | | | 18 | D41994P | 1 | | | 115-199 |
| 0008 | 20 | | GA | | 39-0 | 74-31-21 | D40032J | | | 17 | SM00006 | | 9 | | 001-099 |
| 0008 | 20 | | GA | | 48-0 | 74-31-21 | D40032J | | | 17 | D41994P | 2 | | | 115-199 |
| 0009 | 22 | | GA | | 49-0 | 76-11-12 | D40032J | | | 36 | D41994P | 6 | | | 001-099 |
| 0009 | 22 | | GA | | 48-0 | 76-11-12 | D40032J | | | 36 | D41994P | 6 | | | 115-199 |
| 0010 | 22 | | GA | | 49-0 | 76-11-12 | D40032J | | | 37 | D41994P | 7 | | | 001-099 |
| 0010 | 22 | | GA | | 48-0 | 76-11-12 | D40032J | | | 37 | D41994P | 7 | | | 115-199 |
| 0012 | 24 | | GK | | 26-0 | 78-36-21 | D41736P | | | 18 | D41994P | 31 | | | 001-003 |
| 0012 | 24 | | GK | | 26-0 | 78-36-21 | D41736P | | | 18 | D41994P | 41 | | | 004-099, 115-199 |
| 0013 | 24 | | GK | | 25-0 | 78-36-21 | D41736P | | | 19 | D42018P | 10 | | | 001-099 |
| 0013 | 24 | | GK | | 24-0 | 78-36-21 | D41736P | | | 19 | D42018P | 10 | | | 115-199 |
| 0014 | 22 | | GA | | 49-0 | 78-36-21 | D40032J | | | 35 | D41994P | 8 | | | 001-099 |
| 0014 | 22 | | GA | | 48-0 | 78-36-21 | D40032J | | | 35 | D41994P | 8 | | | 115-199 |
| 0015 | 22 | | GA | | 49-0 | 78-36-21 | D40032J | | | 34 | D41994P | 9 | | | 001-099 |
| 0015 | 22 | | GA | | 48-0 | 78-36-21 | D40032J | | | 34 | D41994P | 9 | | | 115-199 |
| 0016 | 22 | | GA | | 23-0 | 26-11-22 | D41992P | | | 3 | D41736P | 55 | | | 001-099 |
| 0016 | 22 | | GA | | 23-0 | 26-11-22 | D41992P | | | 1 | D41736P | 20 | | | 115-199 |
| 0017 | 22 | | GA | | 53-0 | 26-11-22 | D41992P | | | 2 | D40046J | 5 | | | 001-099 |
| 0017 | 20 | | GA | | 53-0 | 26-11-22 | D41992P | | | 2 | D40046J | 5 | | | 115-199 |
| 0018 | 22 | | GA | | 53-0 | 26-11-22 | D41992P | | | 14 | D40046J | 2 | | | 001-099 |
| 0018 | 20 | | GA | | 53-0 | 26-11-22 | D41992P | | | 14 | D40046J | 2 | | | 115-199 |
| 0019 | 22 | | GA | | 23-0 | 26-12-21 | D41736P | | | 22 | D41992P | 4 | | | 001-099 |
| 0019 | 22 | | GA | | 23-0 | 26-12-21 | D41992P | | | 4 | D41736P | 22 | | | 115-199 |
| 0020 | 20 | | GA | | 53-0 | SPARE | D41992P | | | 5 | D40046J | 6 | | | 001-099 |
| 0021 | 22 | | GA | | 53-0 | 26-12-21 | D41992P | | | 6 | D40046J | 3 | | | ALL |
| 0022 | 22 | | GA | | 53-0 | 26-12-21 | D41992P | | | 7 | D40046J | 4 | | | ALL |
| 0023 | 22 | | GA | | 23-0 | 26-11-21 | D41992P | | | 8 | D41736P | 25 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4220 | 286N4220 | | | | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC (continued) | | | | | | | | | | | | |
| 0024 | 22 | | GA | | 23-0 | 26-11-21 | D41992P | | | | | D41736P | 26 | | | ALL | |
| 0025 | 22 | | GA | | 10-0 | 77-12-42 | D41994P | | | | | D42002P | 4 | | | 001-099 | |
| 0025 | 22 | | GA | | 9-0 | 77-12-42 | D41994P | | | | | D42002P | 4 | | | 115-199 | |
| 0026 | 22 | | GA | | 73-0 | 29-33-11 | D40370J | | | | | D42018P | 39 | | | 001-099 | |
| 0026 | 22 | | GA | | 140-0 | 29-33-11 | D40370J | | | | | D42028P | 1 | | | 115-199 | |
| 0030 | 22 | | GA | | 73-0 | 29-33-11 | D40370J | | | | | D42018P | 38 | | | 001-099 | |
| 0030 | 22 | | GA | | 140-0 | 29-33-11 | D40370J | | | | | D42028P | 5 | | | 115-199 | |
| 0031 | 22 | | GA | | 73-0 | 29-33-11 | D40370J | | | | | D42018P | 40 | | | 001-099 | |
| 0031 | 22 | | GA | | 140-0 | 29-33-11 | D40370J | | | | | D42028P | 6 | | | 115-199 | |
| 0032 | 22 | | GA | | 73-0 | 29-33-11 | D40370J | | | | | D42018P | 41 | | | 001-099 | |
| 0032 | 22 | | GA | | 140-0 | 29-33-11 | D40370J | | | | | D42028P | 7 | | | 115-199 | |
| 0033 | 22 | | GA | | 73-0 | 29-33-11 | D40370J | | | | | D42018P | 44 | | | 001-099 | |
| 0033 | 22 | | GA | | 140-0 | 29-33-11 | D40370J | | | | | D42028P | 8 | | | 115-199 | |
| 0034 | 22 | | GA | | 73-0 | 29-33-11 | D40370J | | | | | D42018P | 43 | | | 001-099 | |
| 0034 | 22 | | GA | | 140-0 | 29-33-11 | D40370J | | | | | D42028P | 9 | | | 115-199 | |
| 0035 | 22 | | GA | | 73-0 | 29-33-11 | D40370J | | | | | D42018P | 42 | | | 001-099 | |
| 0035 | 22 | | GA | | 140-0 | 29-33-11 | D40370J | | | | | D42028P | 10 | | | 115-199 | |
| 0036 | 22 | | GA | | 54-0 | 26-18-21 | D41116J | | | | | D42002P | 5 | | | 001-099 | |
| 0036 | 20 | | GA | | 54-0 | 26-18-21 | D41116J | | | | | D42002P | 5 | | | 115-199 | |
| 0037 | 22 | | GA | | 54-0 | 26-18-21 | D41116J | | | | | D42002P | 6 | | | 001-099 | |
| 0037 | 20 | | GA | | 54-0 | 26-18-21 | D41116J | | | | | D42002P | 6 | | | 115-199 | |
| 0038 | 22 | | GA | | 54-0 | 26-18-21 | D41116J | | | | | D42002P | 7 | | | 001-099 | |
| 0038 | 20 | | GA | | 54-0 | 26-18-21 | D41116J | | | | | D42002P | 7 | | | 115-199 | |
| 0039 | 22 | | GA | | 54-0 | 26-18-21 | D41116J | | | | | D42002P | 8 | | | 001-099 | |
| 0039 | 20 | | GA | | 54-0 | 26-18-21 | D41116J | | | | | D42002P | 8 | | | 115-199 | |
| 0040 | 22 | | GA | | 27-0 | 31-51-21 | D41992P | | | | | D42018P | 11 | | | ALL | |
| 0041 | 22 | | GA | | 27-0 | 31-51-21 | D41992P | | | | | D42018P | 12 | | | ALL | |
| 0042 | 22 | | GA | | 48-0 | 31-51-41 | D42018P | | | | | S00459 | 2NO | B | | 001-099 | |
| 0042 | 22 | | GA | | 47-0 | 31-51-41 | D42018P | | | | | S00459 | 2NO | B | | 115-199 | |
| 0043 | 20 | | GA | | 11-0 | 31-51-41 | S00459 | 2C | B | | | GD02037 | DC.. | E | | 001-099 | |
| 0043 | 20 | | GA | | 8-0 | 31-51-41 | S00459 | 2C | B | | | GD02037 | DC.. | E | | 115-199 | |
| 0044 | 20 | | GA | | 70-0 | 33-31-11 | D41994P | | | | | D40370J | 24 | | | 001-099 | |
| 0044 | 20 | | GA | | 43-0 | SPARE | D40032J | | | | | D41736P | 5 | | | 115-199 | |
| 0045 | 20 | | GA | | 43-0 | SPARE | D40032J | | | | | D41736P | 6 | | | 115-199 | |
| 0046 | 22 | | GA | | 44-0 | 29-32-21 | D41736P | | | | | D40032J | 10 | | | 001-099 | |
| 0046 | 20 | | GA | | 43-0 | 29-32-21 | D40032J | | | | | D41736P | 27 | | | 115-199 | |
| 0047 | 22 | | GA | | 30-0 | 26-15-11 | D42002P | | | | | D41992P | 12 | | | 001-099 | |
| 0047 | 22 | | GA | | 29-0 | 26-15-11 | D42002P | | | | | D41992P | 12 | | | 115-199 | |
| 0048 | 22 | | GA | | 32-0 | 28-21-23 | D40370J | | | | | SP00516 | | 9 | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4220 | 286N4220 | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC (continued) | | | | | | | | | | | | | |
| 0048 | 22 | GA | | | 31-0 | 28-21-23 | D40370J | | 1 | | SP00516 | | 9 | | 115-199 |
| 0049 | 20 | GA | | | 32-0 | 28-21-23 | D40370J | | 20 | | SP01016 | | 9 | | 001-099 |
| 0049 | 20 | GA | | | 31-0 | 28-21-23 | D40370J | | 20 | | SP01016 | | 9 | | 115-199 |
| 0050 | 20 | GA | | | 46-0 | 74-31-21 | D03574 | | 14 | | D41994P | 19 | | | 115-199 |
| 0051 | 20 | GA | | | 46-0 | 74-31-21 | D03574 | | 5 | | D41994P | 18 | | | 115-199 |
| 0053 | 20 | GA | | | 5-0 | 74-31-21 | D03574 | | 11 | | GD00608 | DC.. | 2 | | 001-099 |
| 0053 | 20 | GA | | | 5-0 | 74-31-21 | D03574 | | 11 | | GD00604 | DC.. | 2 | | 115-199 |
| 0054 | 20 | GA | | | 7-0 | 74-31-21 | D03574 | | 6 | | TB0114X | D013 | BJ | | 001-099 |
| 0054 | 20 | GA | | | 6-0 | 74-31-21 | D03574 | | 6 | | TB0114X | D013 | BJ | | 115-199 |
| 0055 | 22 | GA | | | 49-0 | 30-21-11 | D41994P | | 5 | | D40032J | 13 | | | 001-099 |
| 0056 | 20 | GA | | | 47-0 | 74-31-21 | D41994P | | 19 | | D03574 | 14 | | | 001-099 |
| 0057 | 20 | GA | | | 47-0 | 80-11-21 | D03574 | | 13 | | D41994P | 10 | | | 001-099 |
| 0057 | 20 | GA | | | 46-0 | 80-11-21 | D03574 | | 13 | | D41994P | 10 | | | 115-199 |
| 0058 | 20 | GA | | | 47-0 | 80-11-21 | D03574 | | 7 | | D41994P | 11 | | | 001-099 |
| 0058 | 20 | GA | | | 46-0 | 80-11-21 | D03574 | | 7 | | D41994P | 11 | | | 115-199 |
| 0059 | 20 | GA | | | 47-0 | 80-11-21 | D03574 | | 12 | | D41994P | 12 | | | 001-099 |
| 0059 | 20 | GA | | | 46-0 | 80-11-21 | D03574 | | 12 | | D41994P | 12 | | | 115-199 |
| 0060 | 20 | GA | | | 47-0 | 80-11-21 | D03574 | | 9 | | D41994P | 17 | | | 001-099 |
| 0060 | 20 | GA | | | 5-0 | 80-11-21 | D03574 | | 9 | | GD00604 | DC.. | 2 | | 115-199 |
| 0061 | 24 | GK | | | 47-0 | 80-11-21 | D03574 | | 16 | | D41994P | 13 | | | 001-099 |
| 0061 | 24 | GK | | | 46-0 | 80-11-21 | D03574 | | 16 | | D41994P | 13 | | | 115-199 |
| 0062 | 22 | GA | | | 20-0 | 30-21-11 | D41736P | | 31 | | D41994P | 14 | | | ALL |
| 0063 | 22 | GA | | | 23-0 | 30-21-11 | D41736P | | 32 | | D42002P | 17 | | | ALL |
| 0064 | 22 | GA | | | 20-0 | 30-21-11 | D41736P | | 33 | | D41994P | 15 | | | ALL |
| 0065 | 22 | GA | | | 10-0 | 30-21-11 | D42002P | | 16 | | D41994P | 26 | | | 001-099 |
| 0065 | 22 | GA | | | 9-0 | 30-21-11 | D42002P | | 16 | | D41994P | 26 | | | 115-199 |
| 0066 | 24 | GK | | | 27-0 | 78-36-21 | D41994P | | 36 | | D42018P | 16 | | | 001-099 |
| 0066 | 24 | GK | | | 27-0 | 78-36-21 | D41994P | | 16 | | D42018P | 16 | | | 115-199 |
| 0067 | 24 | GK | | | 20-0 | 78-36-21 | D41994P | | 35 | | D41736P | 24 | | | 001-099 |
| 0067 | 24 | GK | | | 20-0 | 78-36-21 | D41994P | | 17 | | D41736P | 24 | | | 115-199 |
| 0068 | 22 | GA | | | 23-0 | 26-16-11 | D41992P | | 13 | | D41736P | 35 | | | ALL |
| 0069 | 22 | GA | | | 7-0 | 33-16-52 | D03574 | | 4 | | TB0114Z | 21 | BJ | | 001-099 |
| 0069 | 22 | GA | | | 6-0 | 33-16-52 | D03574 | | 4 | | TB0114Z | 21 | BJ | | 115-199 |
| 0070 | 18 | GA | | | 15-0 | 32-35-11 | D42018P | | 17 | 18 | SP01110 | | 9 | | 001-099 |
| 0070 | 20 | GA | | | 15-0 | 32-35-11 | D42018P | | 17 | | SP01110 | | 9 | | 115-199 |
| 0071 | 20 | GA | | | 74-0 | 32-12-12 | D42018P | | 18 | | D40370J | 28 | | | 001-099 |
| 0071 | 20 | GA | | | 75-0 | 32-12-12 | D42018P | | 18 | | D40370J | 28 | | | 115-199 |
| 0072 | 20 | GA | | | 74-0 | 32-35-11 | D42018P | | 19 | | D40370J | 29 | | | 001-099 |
| 0072 | 20 | GA | | | 75-0 | 32-35-11 | D42018P | | 19 | | D40370J | 29 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | |
|--------------|-----------------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| Wire No. | GA CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W4220 | 286N4220 | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC (continued) | | | | | | | | | | | | | |
| 0073 | 22 | GA | 40-0 | 32-44-11 | D41736P | 47 | | | D40784P | 3 | | | 001-099 | | |
| 0073 | 24 | GK | 4-0 | 31-31-31 | S10308 | 1C | B | | SM00101 | | 9 | | 115-199 | | |
| 0074 | 20 | GA | 11-0 | 33-13-51 | TB0100X | C002 | BJ | | D40784P | 4 | | | 001-099 | | |
| 0074 | 24 | GK | 4-0 | 31-31-31 | S10309 | 1C | B | | SM00101 | | 9 | | 115-199 | | |
| 0075Y | 20 | QB | 39-0 | 27-41-21 | D42020P | 1 | | | D40782P | 8 | | | 001-099 | | |
| 0076 | 22 | GA | 26-0 | 26-16-11 | D41992P | 15 | | | D41994P | 25 | | | ALL | | |
| 0077 | 24 | GK | 44-0 | 31-31-31 | D42018P | 33 | | | S10309 | 1NO | B | | 115-199 | | |
| 0077Y | 20 | QB | 39-0 | 27-41-21 | D42020P | 2 | | | D40782P | 9 | | | 001-099 | | |
| 0078 | 24 | GK | 49-0 | 73-21-21 | D41736P | 36 | | | SM00001 | | 9 | | 001-099 | | |
| 0078 | 24 | GK | 43-0 | 73-21-21 | SM00001 | | 9 | | D41736P | 36 | | | 115-199 | | |
| 0079 | 18 | GA | 7-0 | 73-21-21 | D03574 | 20 | 18 | | TB0114F | A006 | 2 | | 001-099 | | |
| 0079 | 18 | GA | 29-0 | 73-21-21 | D03574 | 20 | 18 | | TB0159F | A006 | 2 | | 115-199 | | |
| 0080 | 18 | GA | 7-0 | 73-21-21 | D03574 | 38 | 18 | | TB0114F | C006 | 2 | | 001-099 | | |
| 0080 | 18 | GA | 29-0 | 73-21-21 | D03574 | 38 | 18 | | TB0159F | C006 | 2 | | 115-199 | | |
| 0081 | 20 | GA | 7-0 | 73-21-21 | D03574 | 26 | | | GD00604 | DC.. | 2 | | 001-099 | | |
| 0081 | 20 | GA | 5-0 | 73-21-21 | D03574 | 26 | | | GD00604 | DC.. | 2 | | 115-199 | | |
| 0082 | 24 | GK | 7-0 | 73-21-21 | D03574 | 25 | | | TB0114X | A014 | BJ | | 001-099 | | |
| 0082 | 24 | GK | 29-0 | 73-21-21 | D03574 | 25 | | | TB0159X | B001 | BJ | | 115-199 | | |
| 0083 | 18 | GA | 74-0 | 32-12-12 | D40370J | 21 | 18 | | D42018P | 25 | 18 | | 001-099 | | |
| 0083 | 18 | GA | 75-0 | 32-12-12 | D40370J | 21 | 18 | | D42018P | 34 | 18 | | 115-199 | | |
| 0084 | 22 | GA | 74-0 | 32-41-11 | D40370J | 6 | | | D42018P | 26 | | | 001-099 | | |
| 0084 | 22 | GA | 75-0 | 32-41-11 | D40370J | 6 | | | D42018P | 26 | | | 115-199 | | |
| 0085 | 22 | GA | 74-0 | 32-41-11 | D40370J | 7 | | | D42018P | 27 | | | 001-099 | | |
| 0085 | 22 | GA | 75-0 | 32-41-11 | D40370J | 7 | | | D42018P | 27 | | | 115-199 | | |
| 0086 | 22 | GA | 74-0 | 32-41-11 | D40370J | 8 | | | D42018P | 28 | | | 001-099 | | |
| 0086 | 22 | GA | 75-0 | 32-41-11 | D40370J | 8 | | | D42018P | 28 | | | 115-199 | | |
| 0087 | 24 | GK | 25-0 | 32-41-11 | D41736P | 37 | | | D42018P | 7 | | | 001-099 | | |
| 0087 | 24 | GK | 24-0 | 32-41-11 | D41736P | 37 | | | D42018P | 37 | | | 115-199 | | |
| 0088 | 24 | GK | 24-0 | SPARE | D41736P | 38 | | | D42018P | 38 | | | 115-199 | | |
| 0089 | 20 | GA | 65-0 | SPARE | D40370J | 23 | | | D41736P | 40 | | | 115-199 | | |
| 0090 | 20 | GA | 65-0 | SPARE | D40370J | 10 | | | D41736P | 41 | | | 115-199 | | |
| 0091 | 22 | GA | 74-0 | 32-44-11 | D40370J | 4 | | | D42018P | 20 | | | 001-099 | | |
| 0091 | 22 | GA | 75-0 | 32-44-11 | D42018P | 20 | | | D40370J | 4 | | | 115-199 | | |
| 0092 | 22 | GA | 74-0 | 32-44-11 | D40370J | 3 | | | D42018P | 21 | | | 001-099 | | |
| 0092 | 22 | GA | 75-0 | 32-44-11 | D42018P | 21 | | | D40370J | 3 | | | 115-199 | | |
| 0093 | 22 | GA | 74-0 | 32-44-11 | D40370J | 22 | | | D42018P | 22 | | | 001-099 | | |
| 0093 | 22 | GA | 75-0 | 32-44-11 | D42018P | 22 | | | D40370J | 22 | | | 115-199 | | |
| 0094 | 22 | GA | 92-0 | 32-44-11 | D40370J | 2 | | | S00459 | 1NC | B | | 001-099 | | |
| 0094 | 22 | GA | 93-0 | 32-44-11 | S00459 | 1NC | B | | D40370J | 2 | | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4220 | 286N4220 | | | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC (continued) | | | | | | | | | | | |
| 0095 | 22 | GA | | | 92-0 | 32-44-11 | D40370J | | 5 | | S00459 | 1NO | B | | 001-099 |
| 0095 | 22 | GA | | | 93-0 | 32-44-11 | S00459 | | 1NO | B | D40370J | 5 | | | 115-199 |
| 0096 | 22 | GA | | | 48-0 | 32-44-11 | D42018P | | 23 | | S00459 | 1C | B | | 001-099 |
| 0096 | 22 | GA | | | 47-0 | 32-44-11 | S00459 | | 1C | B | D42018P | 23 | | | 115-199 |
| 0097 | 20 | GA | | | 47-0 | 74-31-21 | D41994P | | 18 | | D03574 | 5 | | | 001-099 |
| 0097 | 24 | GK | | | 45-0 | 31-31-31 | D42018P | | 31 | | S10308 | 1NO | B | | 115-199 |
| 0098 | 24 | GK | | | 41-0 | 31-31-31 | D42018P | | 32 | | SM00101 | | 9 | | 115-199 |
| 0100 | 20 | GA | | | 29-0 | 29-21-31 | D42002P | | 9 | | D04514 | 3 | | | 001-099 |
| 0100 | 18 | GA | | | 29-0 | 29-21-31 | D42002P | | 9 | 18 | D04514 | 3 | 18 | | 115-199 |
| 0101 | 20 | GA | | | 33-0 | 29-21-31 | D42002P | | 20 | | D42094P | 2 | | | 001-099 |
| 0101 | 18 | GA | | | 30-0 | 29-21-31 | D42002P | | 20 | 18 | D42094P | 2 | | | 115-199 |
| 0102 | 12 | GA | | | 6-1 | 29-21-31 | SM00008 | | 9 | | SP01524 | | 9 | | 115-199 |
| 0103 | 20 | GA | | | 1-0 | 29-21-31 | SM00004 | | 9 | | D04514 | 1 | | | 001-099 |
| 0103 | 18 | GA | | | 26-0 | 29-21-31 | SM00005 | | 9 | | D04514 | 1 | 18 | | 115-199 |
| 0104 | 12 | GA | | | 76-0 | 29-21-31 | D42094P | | 6 | | SM00002 | | 9 | | 001-099 |
| 0104 | 12 | GA | | | 73-3 | 29-21-31 | SM00004 | | 9 | | SM00002 | | 9 | | 115-199 |
| 0105 | 20 | GA | | | 1-0 | 29-21-31 | SM00004 | | 9 | | D04514 | 4 | | | 001-099 |
| 0105 | 18 | GA | | | 26-0 | 29-21-31 | SM00005 | | 9 | | D04514 | 4 | 18 | | 115-199 |
| 0106 | 24 | GK | | | 43-0 | SPARE | D41994P | CAP | Y | | D40784P | 2 | | | 001-003 |
| 0106 | 24 | GK | | | 43-0 | SPARE | D41994P | | 31 | | D40784P | 2 | | | 004-099 |
| 0107 | 20 | GA | | | 6-0 | 29-21-31 | D04514 | | 2 | | GD02327 | DC.. | E | | 001-099 |
| 0107 | 18 | GA | | | 5-0 | 29-21-31 | D04514 | | 2 | 18 | GD02327 | DC.. | E | | 115-199 |
| 0108 | 22 | GA | | | 74-0 | 29-21-31 | D40370J | | 34 | | D42018P | 24 | | | 001-099 |
| 0108 | 22 | GA | | | 75-0 | 29-21-31 | D40370J | | 34 | | D42018P | 24 | | | 115-199 |
| 0109 | 22 | GA | | | 74-0 | 29-21-31 | D40370J | | 39 | | D42018P | 30 | | | 001-099 |
| 0109 | 22 | GA | | | 75-0 | 29-21-31 | D40370J | | 39 | | D42018P | 30 | | | 115-199 |
| 0110 | 20 | GA | | | 74-0 | 29-21-31 | D40370J | | 32 | | D42018P | 14 | | | 001-099 |
| 0110 | 20 | GA | | | 75-0 | 29-21-31 | D40370J | | 32 | | D42018P | 14 | | | 115-199 |
| 0111 | 20 | GA | | | 76-0 | 29-21-31 | D40370J | | 38 | | D42094P | 7 | | | 001-099 |
| 0111 | 18 | GA | | | 74-0 | 29-21-31 | D40370J | | 38 | 18 | D42094P | 7 | | | 115-199 |
| 0112 | 18 | GA | | | 0-12 | 29-21-31 | D40370J | | 36 | 18 | SM00002 | | 9 | | ALL |
| 0113 | 20 | GA | | | 72-0 | 29-21-31 | D40370J | | 35 | | D04514 | 5 | | | 001-099 |
| 0113 | 18 | GA | | | 73-0 | 29-21-31 | D40370J | | 35 | 18 | D04514 | 5 | 18 | | 115-199 |
| 0114 | 22 | GA | | | 65-0 | 29-21-31 | D40370J | | 30 | | D41736P | 39 | | | ALL |
| 0115 | 22 | GA | | | 65-0 | 29-21-31 | D40370J | | 37 | | D41736P | 45 | | | ALL |
| 0121 | 22 | GA | | | 7-0 | 33-16-62 | D03574 | | 3 | | TB0114Z | 22 | BJ | | 001-099 |
| 0121 | 22 | GA | | | 6-0 | 33-16-62 | D03574 | | 3 | | TB0114Z | 22 | BJ | | 115-199 |
| 0125 | 20 | GA | | | 5-0 | 80-11-21 | D03574 | | 28 | | GD00608 | ST.. | 2 | | ALL |
| 0126 | 20 | GA | | | 50-0 | 36-11-31 | D41116J | | 1 | | D41994P | 24 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4220 | 286N4220 | | | | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC (continued) | | | | | | | | | | | |
| 0126 | 20 | | GA | | 49-0 | 36-11-31 | D41116J | | | | | D41994P | 24 | | | 115-199 |
| 0127 | 20 | | GA | | 50-0 | 36-11-31 | D41116J | | | | | D41994P | 23 | | | 001-099 |
| 0127 | 20 | | GA | | 49-0 | 36-11-31 | D41116J | | | | | D41994P | 23 | | | 115-199 |
| 0128 | 20 | | GA | | 50-0 | 36-11-31 | D41116J | | | | | D41994P | 22 | | | 001-099 |
| 0128 | 20 | | GA | | 49-0 | 36-11-31 | D41116J | | | | | D41994P | 22 | | | 115-199 |
| 0129 | 20 | | GA | | 50-0 | 36-11-31 | D41116J | | | | | D41994P | 21 | | | 001-099 |
| 0129 | 20 | | GA | | 49-0 | 36-11-31 | D41116J | | | | | D41994P | 21 | | | 115-199 |
| 0130 | 22 | | GA | | 27-0 | 29-22-11 | D42018P | | 29 | | | D41994P | 27 | | | ALL |
| 0132 | 22 | | GA | | 23-0 | 29-22-11 | TB0121X | | B008 | BJ | | D42094P | 8 | | | 115-199 |
| 0133 | 22 | | GA | | 43-0 | 29-22-11 | TB0121X | | A008 | BJ | | D42002P | 10 | | | 115-199 |
| 0134 | 22 | | GA | | 39-0 | 29-22-11 | TB0121X | | C008 | BJ | | D41994P | 28 | | | 001-099 |
| 0134 | 22 | | GA | | 40-0 | 29-22-11 | TB0121X | | C008 | BJ | | D41994P | 28 | | | 115-199 |
| 0136 | 24 | | GK | | 1-0 | 73-21-21 | D03574 | | 22 | | | SM00001 | | 9 | | 115-199 |
| 0137 | 22 | | GA | | 24-0 | 29-22-11 | TB0121X | | A005 | BJ | | D42094P | 8 | | | 001-099 |
| 0137 | 24 | | GK | | 1-0 | 73-21-21 | D03574 | | 24 | | | SM00001 | | 9 | | 115-199 |
| 0138 | 22 | | GA | | 24-0 | 29-22-11 | TB0121X | | B005 | BJ | | D42094P | 3 | | | 001-099 |
| 0138 | 22 | | GA | | 23-0 | 29-22-11 | D42094P | | 3 | | | TB0121X | A005 | BJ | | 115-199 |
| 0139 | 22 | | GA | | 24-0 | 29-22-11 | TB0121X | | C005 | BJ | | D42094P | 4 | | | 001-099 |
| 0139 | 22 | | GA | | 23-0 | 29-22-11 | D42094P | | 4 | | | TB0121X | B005 | BJ | | 115-199 |
| 0140 | 22 | | GA | | 39-0 | 29-22-11 | TB0121X | | B008 | BJ | | D41994P | 29 | | | 001-099 |
| 0140 | 22 | | GA | | 23-0 | 29-22-11 | D42094P | | 5 | | | TB0121X | C005 | BJ | | 115-199 |
| 0141 | 22 | | GA | | 43-0 | 29-22-11 | TB0121X | | A008 | BJ | | D42002P | 13 | | | 001-099 |
| 0141 | 16 | | GA | | 0-8 | 29-21-31 | D42094P | | 1 | | | SM00008 | | 9 | | 115-199 |
| 0142 | 20 | | GA | | 27-0 | 29-21-31 | D41994P | | 20 | | | SM00004 | | 9 | | 001-099 |
| 0142 | 16 | | GA | | 0-8 | 29-21-31 | D42094P | | 6 | | | SM00004 | | 9 | | 115-199 |
| 0143 | 18 | | GA | | 74-0 | 32-12-12 | D40370J | | 25 | 18 | | D42018P | 31 | 18 | | 001-099 |
| 0143 | 18 | | GA | | 75-0 | 32-12-12 | D40370J | | 25 | 18 | | D42018P | 35 | 18 | | 115-199 |
| 0144 | 24 | | GK | | 1-0 | 73-21-21 | D03574 | | 22 | | | SM00001 | | 9 | | 001-099 |
| 0144 | 20 | | GA | | 70-0 | 33-31-11 | D41994P | | 32 | | | D40370J | 24 | | | 115-199 |
| 0145 | 20 | | GA | | 47-0 | 74-31-21 | D03574 | | 31 | | | D41994P | 32 | | | 001-099 |
| 0145 | 20 | | GA | | 46-0 | 74-31-21 | D03574 | | 31 | | | D41994P | 31 | | | 115-199 |
| 0146 | 20 | | GA | | 36-0 | 74-31-21 | D03574 | | 29 | | | SM00006 | | 9 | | 001-099 |
| 0147 | 20 | | GA | | 13-0 | 74-31-21 | D41994P | | 33 | | | SM00006 | | 9 | | 001-099 |
| 0148 | 24 | | GK | | 1-0 | 73-21-21 | D03574 | | 24 | | | SM00001 | | 9 | | 001-099 |
| 0149 | 22 | | GA | | 44-0 | SPARE | D40032J | | 40 | | | D41736P | 49 | | | 001-099 |
| 0150 | 22 | | GA | | 44-0 | SPARE | D40032J | | 41 | | | D41736P | 50 | | | 001-099 |
| 0151 | 22 | | GA | | 44-0 | SPARE | D40032J | | 42 | | | D41736P | 51 | | | 001-099 |
| 0158 | 20 | | GA | | 43-0 | SPARE | D40032J | | 1 | | | D41736P | 47 | | | 115-199 |
| 0160 | 20 | | GA | | 1-0 | 29-21-31 | D41994P | | 20 | | | SM00005 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4220 | 286N4220 | | | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC (continued) | | | | | | | | | | | |
| 0170 | 20 | | GA | | 47-0 | 74-31-21 | D03574 | 10 | | | D41994P | 30 | | | 001-099 |
| 0170 | 20 | | GA | | 46-0 | 74-31-21 | D03574 | 10 | | | D41994P | 30 | | | 115-199 |
| 0172 | 24 | | GK | | 32-0 | 78-36-21 | D41994P | 16 | | | D42018P | 9 | | | 001-099 |
| 0172 | 24 | | GK | | 32-0 | 78-36-21 | D42018P | 9 | | | D41994P | 29 | | | 115-199 |
| 0175 | 20 | | GA | | 70-0 | 28-22-32 | D41994P | 48 | | | D40368J | 2 | | | 009-099 |
| 0176 | 20 | | GA | | 70-0 | 28-22-32 | D41994P | 49 | | | D40368J | 3 | | | 009-099 |
| 0177 | 20 | | GA | | 70-0 | 28-22-32 | D41994P | 50 | | | D40368J | 4 | | | 009-099 |
| 0178 | 20 | | GA | | 48-0 | 78-36-21 | D40032J | 33 | | | D41994P | 51 | | | 003-099 |
| 1001 | 22 | | GT | AP | 73-0 | 29-33-11 | D40368J | 1 | VN | | D42134P | 1 | | | 001-099 |
| 1001 | 22 | | GT | AP | 140-0 | 29-33-11 | D40368J | 1 | VN | | D40518P | 1 | | | 115-199 |
| 1001Z | | | | AP | 0-0 | 29-33-11 | D40368J | = C1 | | | D42134P | = C1 | | | 001-099 |
| 1001Z | | | | AP | 0-0 | 29-33-11 | D40368J | = C1 | | | D40518P | = C1 | | | 115-199 |
| 1003 | 20 | | GE | T | 49-0 | 76-11-21 | D40032J | 19 | | | D41994P | 3 | | | ALL |
| 1003Z | | | | T | 0-0 | 76-11-21 | D40032J | S/R | | | GD03620 | ST.. | E | | ALL |
| 2001B | 22 | | GB | CC | 54-0 | 78-36-21 | D42018P | 2 | | | D40280J | 2 | | | 001-099 |
| 2001B | 22 | | GB | AG | 54-0 | 78-36-21 | D40280J | 2 | | | D42018P | 2 | | | 115-199 |
| 2001R | 22 | | GB | CC | 0-0 | 78-36-21 | D42018P | 1 | | | D40280J | 1 | | | 001-099 |
| 2001R | 22 | | GB | AG | 0-0 | 78-36-21 | D40280J | 1 | | | D42018P | 1 | | | 115-199 |
| 2002B | 22 | | GB | CD | 54-0 | 78-36-21 | D42018P | 4 | | | D40280J | 4 | | | 001-099 |
| 2002B | 22 | | GB | AH | 54-0 | 78-36-21 | D40280J | 4 | | | D42018P | 4 | | | 115-199 |
| 2002R | 22 | | GB | CD | 0-0 | 78-36-21 | D42018P | 3 | | | D40280J | 3 | | | 001-099 |
| 2002R | 22 | | GB | AH | 0-0 | 78-36-21 | D40280J | 3 | | | D42018P | 3 | | | 115-199 |
| 2003B | 22 | | GB | CE | 54-0 | 78-36-21 | D42018P | 6 | | | D40280J | 6 | | | 001-099 |
| 2003B | 22 | | GB | AJ | 54-0 | 78-36-21 | D40280J | 6 | | | D42018P | 6 | | | 115-199 |
| 2003R | 22 | | GB | CE | 0-0 | 78-36-21 | D42018P | 5 | | | D40280J | 5 | | | 001-099 |
| 2003R | 22 | | GB | AJ | 0-0 | 78-36-21 | D40280J | 5 | | | D42018P | 5 | | | 115-199 |
| 2004B | 22 | | GB | CF | 54-0 | 78-36-21 | D42018P | 8 | | | D40280J | 8 | | | 001-099 |
| 2004B | 22 | | GB | AK | 54-0 | 78-36-21 | D40280J | 8 | | | D42018P | 8 | | | 115-199 |
| 2004R | 22 | | GB | CF | 0-0 | 78-36-21 | D42018P | 15 | | | D40280J | 7 | | | 001-099 |
| 2004R | 22 | | GB | AK | 0-0 | 78-36-21 | D40280J | 7 | | | D42018P | 7 | | | 115-199 |
| 2005B | 20 | | GB | AM | 54-0 | SPARE | D40280J | 10 | | | D42018P | 15 | | | 115-199 |
| 2005R | 20 | | GB | AM | 0-0 | SPARE | D40280J | 9 | | | D42018P | 41 | | | 115-199 |
| 2006B | 20 | | GB | AR | 65-0 | 29-32-41 | D41736P | 23 | | | D40370J | 33 | | | 001-099 |
| 2006B | 20 | | GB | AR | 66-0 | 29-32-41 | D41736P | 23 | | | D40370J | 33 | | | 115-199 |
| 2006R | 20 | | GB | AR | 0-0 | 29-32-41 | D41736P | 21 | | | D40370J | 31 | | | ALL |
| 2007B | 24 | | GL | AT | 41-0 | 27-51-41 | D42228P | 2 | | | D40782P | 12 | | | 001-099 |
| 2007R | 24 | | GL | AT | 0-0 | 27-51-41 | D42228P | 1 | | | D40782P | 5 | | | 001-099 |
| 2501B | 22 | | GU | AB | 44-0 | 79-34-11 | D41736P | 14 | | | D40032J | 31 | | | 001-099 |
| 2501B | 22 | | GU | AF | 43-0 | 79-34-11 | D40032J | 31 | | | D41736P | 14 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4220 | 286N4220 | | | | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC (continued) | | | | | | | | | | | | |
| 2501R | 22 | GU | AB | | 0-0 | 79-34-11 | D41736P | | | | | D40032J | 32 | | | 001-099 | |
| 2501R | 22 | GU | AF | | 0-0 | 79-34-11 | D40032J | | | | | D41736P | 15 | | | 115-199 | |
| 2501Z | | | AB | | 0-0 | 79-34-11 | D41736P | | | | | D40032J | S/R | | | 001-099 | |
| 2501Z | | | AF | | 0-0 | 79-34-11 | D40032J | S/R | | | | D41736P | 16 | | | 115-199 | |
| 2502B | 24 | G2 | AA | | 23-0 | 77-12-31 | D41736P | | | | | D42002P | 14 | | | 001-099 | |
| 2502B | 24 | G2 | AN | | 23-0 | 77-12-31 | D41736P | | | | | D42002P | 14 | | | 115-199 | |
| 2502R | 24 | G2 | AA | | 0-0 | 77-12-31 | D41736P | | | | | D42002P | 10 | | | 001-099 | |
| 2502R | 24 | G2 | AN | | 0-0 | 77-12-31 | D41736P | | | | | D42002P | 13 | | | 115-199 | |
| 2502Z | | | AA | | 0-0 | 77-12-31 | D41736P | | | | | D42002P | 15 | | | 001-099 | |
| 2502Z | | | AN | | 0-0 | 77-12-31 | D41736P | | | | | D42002P | 15 | | | 115-199 | |
| 2503B | 22 | GU | AC | | 44-0 | 79-34-11 | D41736P | | | | | D40032J | 6 | | | 001-099 | |
| 2503B | 22 | GU | AS | | 43-0 | 79-34-11 | D41736P | | | | | D40032J | 6 | | | 115-199 | |
| 2503R | 22 | GU | AC | | 0-0 | 79-34-11 | D41736P | | | | | D40032J | 5 | | | 001-099 | |
| 2503R | 22 | GU | AS | | 0-0 | 79-34-11 | D41736P | | | | | D40032J | 5 | | | 115-199 | |
| 2503Z | | | AC | | 0-0 | 79-34-11 | D41736P | | | | | D40032J | S/R | | | 001-099 | |
| 2503Z | | | AS | | 0-0 | 79-34-11 | D41736P | | | | | D40032J | S/R | | | 115-199 | |
| 2504B | 22 | GU | AD | | 44-0 | SPARE | D41736P | | | | | D40032J | 1 | | | 001-099 | |
| 2504R | 22 | GU | AD | | 0-0 | SPARE | D41736P | | | | | D40032J | 2 | | | 001-099 | |
| 2504Z | | | AD | | 0-0 | SPARE | D41736P | | | | | D40032J | 4 | | | 001-099 | |
| 2508B | 20 | GU | CK | | 43-0 | SPARE | D40032J | | | | | D41736P | 48 | | | 115-199 | |
| 2508R | 20 | GU | CK | | 0-0 | SPARE | D40032J | | | | | D41736P | 49 | | | 115-199 | |
| 2508Z | | | CK | | 0-0 | SPARE | D40032J | | | | | D41736P | 50 | | | 115-199 | |
| 3001B | 22 | GC | CB | | 44-0 | 73-31-11 | D41736P | | | | | D40032J | 15 | | | 001-099 | |
| 3001B | 22 | GC | AB | | 43-0 | 73-31-11 | D40032J | | | | | D41736P | 3 | | | 115-199 | |
| 3001R | 22 | GC | CB | | 0-0 | 73-31-11 | D41736P | | | | | D40032J | 14 | | | 001-099 | |
| 3001R | 22 | GC | AB | | 0-0 | 73-31-11 | D40032J | | | | | D41736P | 2 | | | 115-199 | |
| 3001Y | 22 | GC | CB | | 0-0 | 73-31-11 | D41736P | | | | | D40032J | 16 | | | 001-099 | |
| 3001Y | 22 | GC | AB | | 0-0 | 73-31-11 | D40032J | | | | | D41736P | 4 | | | 115-199 | |
| 3002B | 22 | GC | CG | | 44-0 | 79-31-11 | D41736P | | | | | D40032J | 26 | | | 001-099 | |
| 3002B | 22 | GC | AD | | 43-0 | 79-31-11 | D40032J | | | | | D41736P | 9 | | | 115-199 | |
| 3002R | 22 | GC | CG | | 0-0 | 79-31-11 | D41736P | | | | | D40032J | 27 | | | 001-099 | |
| 3002R | 22 | GC | AD | | 0-0 | 79-31-11 | D40032J | | | | | D41736P | 10 | | | 115-199 | |
| 3002Y | 22 | GC | CG | | 0-0 | 79-31-11 | D41736P | | | | | D40032J | 25 | | | 001-099 | |
| 3002Y | 22 | GC | AD | | 0-0 | 79-31-11 | D40032J | | | | | D41736P | 8 | | | 115-199 | |
| 3003B | 22 | GC | CH | | 44-0 | 79-32-11 | D41736P | | | | | D40032J | 28 | | | 001-099 | |
| 3003B | 22 | GC | AE | | 43-0 | 79-32-11 | D40032J | | | | | D41736P | 12 | | | 115-199 | |
| 3003R | 22 | GC | CH | | 0-0 | 79-32-11 | D41736P | | | | | D40032J | 29 | | | 001-099 | |
| 3003R | 22 | GC | AE | | 0-0 | 79-32-11 | D40032J | | | | | D41736P | 11 | | | 115-199 | |
| 3003Y | 22 | GC | CH | | 0-0 | 79-32-11 | D41736P | | | | | D40032J | 30 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4220 | 286N4220 | | | E/E SHELF DISC TO RIGHT WHEEL WELL AND WING BODY DISC (continued) | | | | | | | | | | | |
| 3003Y | 22 | GC | AE | | 0-0 | 79-32-11 | D40032J | 30 | | | D41736P | 13 | | | 115-199 |
| 4001B | 24 | GN | CA | | 41-0 | 27-51-41 | D42228P | 4 | | | D40782P | 7 | | | 001-099 |
| 4001G | 24 | GN | CA | | 0-0 | 27-51-41 | D42228P | 6 | | | D40782P | 11 | | | 001-099 |
| 4001R | 24 | GN | CA | | 0-0 | 27-51-41 | D42228P | 3 | | | D40782P | 6 | | | 001-099 |
| 4001Y | 24 | GN | CA | | 0-0 | 27-51-41 | D42228P | 5 | | | D40782P | 10 | | | 001-099 |
| YAAA | | | | | 0-0 | 26-12-21 | D40046J | S/R | | | GD03108 | ST.. | E | * | 001-099 |
| YAAA | | | | | 0-0 | 29-32-21 | GD03108 | ST.. | E | * | D40032J | S/R | | | 115-199 |
| YAAB | | | | | 0-0 | 26-18-21 | D41116J | S/R | | | GD03108 | ST.. | E | * | 001-099 |
| YAAB | | | | | 0-0 | 26-11-22 | GD03108 | ST.. | E | * | D40046J | S/R | | | 115-199 |
| YAAC | | | | | 0-0 | 29-32-21 | D40032J | S/R | | | GD03108 | ST.. | E | * | 001-099 |
| YAAC | | | | | 0-0 | 78-36-21 | GD03108 | ST.. | E | * | D40280J | S/R | | | 115-199 |
| YAAD | | | | | 0-0 | 78-36-21 | D40280J | S/R | | | GD03108 | ST.. | E | * | 001-099 |
| YAAF | | | | | 0-0 | 26-18-21 | GD03108 | ST.. | E | * | D41116J | S/R | | | 115-199 |
| W4224 | 286N4224 | | | JUMPER BUNDLE FROM D40164P TO D41180P | | | | | | | | | | | |
| 0001 | 22 | GA | | | 78-0 | 27-38-11 | D41180P | 1 | | | D40164P | 1 | | | ALL |
| 0006 | 20 | GA | | | 78-0 | 33-45-11 | D41180P | 8 | | | D40164P | 8 | | | ALL |
| 0007 | 22 | GA | | | 78-0 | 27-23-11 | D40164P | 4 | | | D41180P | 4 | | | ALL |
| 0008 | 22 | GA | | | 78-0 | 27-23-11 | D40164P | 5 | | | D41180P | 5 | | | ALL |
| 0041 | 22 | GA | | | 78-0 | 27-23-21 | D40164P | 7 | | | D41180P | 7 | | | ALL |
| 0042 | 22 | GA | | | 78-0 | 27-23-21 | D40164P | 6 | | | D41180P | 6 | | | ALL |
| 0045 | 20 | GA | | | 78-0 | SPARE | D41180P | 9 | | | D40164P | 9 | | | ALL |
| 1025 | 22 | GT | BC | | 78-0 | 27-38-11 | D41180P | 10 | | | D40164P | 10 | | | ALL |
| 1025Z | | | BC | | 0-0 | 27-38-11 | D41180P | 11 | | | D40164P | 11 | | | ALL |
| 2001B | 22 | GB | AA | | 78-0 | 27-38-11 | D41180P | 3 | | | D40164P | 3 | | | ALL |
| 2001R | 22 | GB | AA | | 0-0 | 27-38-11 | D41180P | 2 | | | D40164P | 2 | | | ALL |
| W4226 | 286N4226 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - C2 | | | | | | | | | | | |
| 0001 | 20 | GA | | | 83-0 | 22-11-32 | D41622P | 22 | | | D40352J | 39 | | | ALL |
| 0002 | 20 | GA | | | 83-0 | 22-11-32 | D41622P | 24 | | | D40352J | 22 | | | ALL |
| 0007 | 22 | GA | | | 38-0 | 28-21-23 | D40352J | 26 | | | SP00508 | | 9 | | 001-099 |
| 0007 | 20 | GA | | | 37-0 | 28-21-23 | D40352J | 26 | | | SP00508 | | 9 | | 115-199 |
| 0008 | 20 | GA | | | 38-0 | 28-21-23 | D40352J | 27 | | | SP01010 | | 9 | | 001-099 |
| 0008 | 20 | GA | | | 37-0 | 28-21-23 | D40352J | 27 | | | SP01010 | | 9 | | 115-199 |
| 0009 | 20 | GA | | | 83-0 | 29-35-11 | D41622P | 13 | | | D40352J | 32 | | | ALL |
| 0010 | 20 | GA | | | 83-0 | 29-35-11 | D41622P | 14 | | | D40352J | 33 | | | ALL |
| 0011 | 20 | GA | | | 83-0 | SPARE | D41622P | 21 | | | D40352J | 34 | | | 001-099 |
| 0011 | 20 | GA | | | 83-0 | SPARE | D41622P | 28 | | | D40352J | 34 | | | 115-199 |
| 0012 | 20 | GA | | | 83-0 | SPARE | D41622P | 23 | | | D40352J | 35 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4226 | 286N4226 | | | E/E BAY TO LEFT WING/BODY AND BODY/SPAR INSTALLATIONS - C2 (continued) | | | | | | | | | | | |
| 0012 | 20 | | GA | | 83-0 | SPARE | D41622P | | 29 | | D40352J | | 35 | | 115-199 |
| 2001B | 20 | | GB | AA | 83-0 | 22-11-31 | D41622P | | 15 | | D40352J | | 19 | | ALL |
| 2001R | 20 | | GB | AA | 0-0 | 22-11-31 | D41622P | | 16 | | D40352J | | 20 | | ALL |
| 2002B | 22 | | GB | AB | 83-0 | 22-13-31 | D41622P | | 18 | | D40352J | | 12 | | ALL |
| 2002R | 22 | | GB | AB | 0-0 | 22-13-31 | D41622P | | 17 | | D40352J | | 11 | | ALL |
| 2003B | 20 | | GB | AC | 83-0 | 29-32-41 | D41622P | | 20 | | D40352J | | 31 | | ALL |
| 2003R | 20 | | GB | AC | 0-0 | 29-32-41 | D41622P | | 19 | | D40352J | | 29 | | ALL |
| 3001B | 22 | | GC | CA | 83-0 | 22-13-31 | D41622P | | 8 | | D40352J | | 14 | | ALL |
| 3001R | 22 | | GC | CA | 0-0 | 22-13-31 | D41622P | | 7 | | D40352J | | 13 | | ALL |
| 3001Y | 22 | | GC | CA | 0-0 | 22-13-31 | D41622P | | 9 | | D40352J | | 15 | | ALL |
| 3002B | 22 | | GC | CB | 83-0 | 22-13-31 | D41622P | | 11 | | D40352J | | 17 | | ALL |
| 3002R | 22 | | GC | CB | 0-0 | 22-13-31 | D41622P | | 10 | | D40352J | | 16 | | ALL |
| 3002Y | 22 | | GC | CB | 0-0 | 22-13-31 | D41622P | | 12 | | D40352J | | 18 | | ALL |
| W4228 | 286N4228 | | | E/E SHELF DISC TO LEFT WING BODY DISC | | | | | | | | | | | |
| 0002 | 22 | | GA | | 84-0 | 76-11-11 | D40002J | | 11 | | D40901P | | 15 | | 001-099 |
| 0002 | 22 | | GA | | 85-0 | 76-11-11 | D40002J | | 11 | | D40901P | | 15 | | 115-199 |
| 0004 | 22 | | GA | | 64-0 | 76-11-11 | D40014J | | 27 | | D41948P | | 2 | | ALL |
| 0005 | 22 | | GA | | 64-0 | 76-11-11 | D40014J | | 28 | | D41948P | | 1 | | ALL |
| 0007 | 22 | | GA | | 36-0 | 76-11-11 | D41948P | | 3 | | D40901P | | 21 | | 115-199 |
| 0008 | 22 | | GA | | 37-0 | 76-11-11 | D41948P | | 4 | | D40901P | | 4 | | 001-099 |
| 0008 | 24 | | GK | | 37-0 | 76-11-11 | D41948P | | 4 | | D40901P | | 4 | | 115-199 |
| 0009 | 22 | | GA | | 20-0 | 76-11-11 | D01594 | | 7 | | D40901P | | 14 | | 001-099 |
| 0009 | 22 | | GA | | 21-0 | 76-11-11 | D01594 | | 7 | | D40901P | | 14 | | 115-199 |
| 0010 | 22 | | GA | | 6-0 | 76-11-11 | D01594 | | 19 | | TB0059X | B004 | BJ | | ALL |
| 0011 | 24 | | GK | | 6-0 | 21-25-11 | D03496 | | 11 | | TB0058X | A011 | BJ | | 001-099 |
| 0011 | 24 | | GK | | 7-0 | 21-25-11 | D03496 | | 11 | | TB0058X | A011 | BJ | | 115-199 |
| 0012 | 22 | | GA | | 65-0 | 28-42-11 | D41738P | | 1 | | D40002J | | 1 | | 001-099 |
| 0012 | 22 | | GA | | 65-0 | 28-42-11 | D40002J | | 1 | | D41738P | | 1 | | 115-199 |
| 0013 | 22 | | GA | | 23-0 | 26-11-11 | D41944P | | 1 | | D41738P | | 2 | | 001-099 |
| 0013 | 22 | | GA | | 22-0 | 26-11-11 | D41944P | | 1 | | D41738P | | 2 | | 115-199 |
| 0014 | 22 | | GA | | 23-0 | 26-11-11 | D41944P | | 2 | | D41738P | | 3 | | 001-099 |
| 0014 | 22 | | GA | | 22-0 | 26-11-11 | D41944P | | 2 | | D41738P | | 3 | | 115-199 |
| 0015 | 22 | | GA | | 23-0 | 26-11-11 | D41944P | | 3 | | D41738P | | 4 | | 001-099 |
| 0015 | 22 | | GA | | 22-0 | 26-11-11 | D41944P | | 3 | | D41738P | | 4 | | 115-199 |
| 0016 | 22 | | GA | | 12-0 | 21-58-12 | D41948P | | 46 | | D41738P | | 5 | | ALL |
| 0017 | 22 | | GA | | 23-0 | 26-11-11 | D41944P | | 5 | | D41738P | | 6 | | 001-099 |
| 0017 | 22 | | GA | | 22-0 | 26-11-11 | D41944P | | 5 | | D41738P | | 6 | | 115-199 |
| 0018 | 22 | | GA | | 28-0 | 26-11-11 | D41944P | | 6 | | D03490 | | 3 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | | 286N4228 | | | | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | |
| 0019 | 22 | GA | | | 28-0 | 26-11-11 | D41944P | | 7 | | TB0158A | C008 | 2 | | 001-099 |
| 0019 | 22 | GA | | | 27-0 | 26-11-11 | D41944P | | 7 | | TB0158A | C008 | 2 | | 115-199 |
| 0020 | 22 | GA | | | 28-0 | 26-11-11 | D41944P | | 8 | | TB0158A | C005 | 2 | | 001-099 |
| 0020 | 22 | GA | | | 27-0 | 26-11-11 | D41944P | | 8 | | TB0158A | C005 | 2 | | 115-199 |
| 0021 | 22 | GA | | | 6-0 | 26-11-11 | D01594 | | 2 | | TB0158A | A009 | 2 | | 001-099 |
| 0021 | 22 | GA | | | 7-0 | 26-11-11 | D01594 | | 2 | | TB0158A | A009 | 2 | | 115-199 |
| 0022 | 22 | GA | | | 6-0 | 26-11-11 | D01594 | | 25 | | TB0158A | A008 | 2 | | 001-099 |
| 0022 | 22 | GA | | | 7-0 | 26-11-11 | D01594 | | 25 | | TB0158A | A008 | 2 | | 115-199 |
| 0023 | 22 | GA | | | 6-0 | 26-11-11 | D03490 | | 4 | | GD01649 | DC.. | 2 | | 001-099 |
| 0023 | 20 | GA | | | 6-0 | 26-11-11 | D03490 | | 4 | | GD01649 | DC.. | 2 | | 115-199 |
| 0024R | 20 | QA | | | 69-0 | 26-11-11 | D41944P | | 9 | | D40014J | | 8 | | 001-099 |
| 0024R | 20 | QA | | | 68-0 | 26-11-11 | D40014J | | 8 | | D41944P | | 9 | | 115-199 |
| 0025R | 20 | QA | | | 69-0 | 26-11-11 | D41944P | | 38 | | D40014J | | 4 | | 001-099 |
| 0025R | 20 | QA | | | 68-0 | 26-11-11 | D40014J | | 4 | | D41944P | | 38 | | 115-199 |
| 0026R | 20 | QA | | | 69-0 | 26-11-11 | D41944P | | 11 | | D40014J | | 6 | | 001-099 |
| 0026R | 20 | QA | | | 68-0 | 26-11-11 | D40014J | | 6 | | D41944P | | 11 | | 115-199 |
| 0027 | 22 | GA | | | 23-0 | SPARE | D41738P | | 7 | | D41944P | | 36 | | 001-099 |
| 0027 | 22 | GA | | | 22-0 | SPARE | D41738P | | 7 | | D41944P | | 36 | | 115-199 |
| 0028 | 22 | GA | | | 28-0 | 26-11-11 | D41944P | | 37 | | D01594 | | 10 | | ALL |
| 0029 | 20 | GA | | | 69-0 | 26-13-11 | D41944P | | 25 | | D40014J | | 2 | | 001-099 |
| 0029 | 22 | GA | | | 68-0 | 26-13-11 | D41944P | | 25 | | D40014J | | 2 | | 115-199 |
| 0030 | 20 | GA | | | 69-0 | 26-13-11 | D41944P | | 14 | | D40014J | | 5 | | 001-099 |
| 0030 | 22 | GA | | | 68-0 | 26-13-11 | D41944P | | 14 | | D40014J | | 5 | | 115-199 |
| 0031 | 22 | GA | | | 23-0 | 26-13-11 | D41944P | | 19 | | D41738P | | 8 | | 001-099 |
| 0031 | 22 | GA | | | 22-0 | 26-13-11 | D41944P | | 19 | | D41738P | | 8 | | 115-199 |
| 0032 | 22 | GA | | | 68-0 | 26-18-11 | D42004P | | 1 | | D40014J | | 13 | | 001-099 |
| 0032 | 20 | GA | | | 68-0 | 26-18-11 | D42004P | | 1 | | D40014J | | 13 | | 115-199 |
| 0033 | 22 | GA | | | 68-0 | 26-18-11 | D42004P | | 2 | | D40014J | | 14 | | 001-099 |
| 0033 | 20 | GA | | | 68-0 | 26-18-11 | D42004P | | 2 | | D40014J | | 14 | | 115-199 |
| 0034 | 20 | GA | | | 6-0 | 28-22-21 | D01594 | | 16 | | TB0059X | C003 | BJ | | ALL |
| 0035 | 20 | GA | | | 6-0 | 28-22-21 | D01594 | | 32 | | TB0059Y | A005 | BJ | | ALL |
| 0036 | 20 | GA | | | 20-0 | 28-22-21 | D01594 | | 33 | | D40901P | | 11 | | 001-099 |
| 0036 | 20 | GA | | | 21-0 | 28-22-21 | D01594 | | 33 | | D40901P | | 11 | | 115-199 |
| 0037 | 20 | GA | | | 28-0 | 28-22-21 | D40901P | | 12 | | D41944P | | 12 | | 001-099 |
| 0037 | 20 | GA | | | 27-0 | 28-22-21 | D40901P | | 12 | | D41944P | | 12 | | 115-199 |
| 0038 | 20 | GA | | | 28-0 | 28-22-21 | TB0059Y | A005 | BJ | | D41944P | | 13 | | 001-099 |
| 0038 | 20 | GA | | | 27-0 | 28-22-21 | TB0059Y | A005 | BJ | | D41944P | | 13 | | 115-199 |
| 0039 | 22 | GA | | | 27-0 | 28-22-21 | D40901P | | 26 | | D42006P | | 1 | | 001-099 |
| 0039 | 22 | GA | | | 26-0 | 28-22-21 | D40901P | | 26 | | D42006P | | 1 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | 286N4228 | | | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | |
| 0040 | 22 | | GA | | 39-0 | 28-22-21 | D40901P | | 24 | | D41738P | | 9 | | 001-099 |
| 0040 | 22 | | GA | | 38-0 | 28-22-21 | D40901P | | 24 | | D41738P | | 9 | | 115-199 |
| 0041 | 20 | | GA | | 13-0 | 28-22-21 | D42006P | | 2 | | D41944P | | 15 | | ALL |
| 0042 | 22 | | GA | | 23-0 | 26-11-12 | D41738P | | 10 | | D41944P | | 16 | | 001-099 |
| 0042 | 22 | | GA | | 22-0 | 26-11-12 | D41738P | | 10 | | D41944P | | 16 | | 115-199 |
| 0043 | 22 | | GA | | 68-0 | 26-11-12 | D41944P | | 10 | | D40026J | | 8 | | 001-099 |
| 0043 | 20 | | GA | | 68-0 | 26-11-12 | D40026J | | 8 | | D41944P | | 10 | | 115-199 |
| 0044 | 22 | | GA | | 68-0 | 26-11-12 | D41944P | | 20 | | D40026J | | 12 | | 001-099 |
| 0044 | 20 | | GA | | 68-0 | 26-11-12 | D40026J | | 12 | | D41944P | | 18 | | 115-199 |
| 0045 | 22 | | GA | | 29-0 | 78-34-11 | D41948P | | 5 | | D42012P | | 5 | | 001-099 |
| 0045 | 22 | | GA | | 27-0 | 78-34-11 | D41948P | | 5 | | D42012P | | 5 | | 115-199 |
| 0046 | 22 | | GA | | 37-0 | SPARE | D41948P | | 6 | | D40901P | CAP | Y | | 001-002, 115-199 |
| 0047 | 22 | | GA | | 37-0 | SPARE | D41948P | | 7 | | D40901P | CAP | Y | | 001-002, 115-199 |
| 0048 | 22 | | GA | | 38-0 | 78-34-11 | D41948P | | 32 | | D01594 | | 39 | | ALL |
| 0049 | 22 | | GA | | 6-0 | 78-34-11 | D01594 | | 20 | | TB0059Y | A006 | BJ | | ALL |
| 0050 | 22 | | GA | | 6-0 | 26-11-11 | D01594 | | 24 | | GD01649 | ST.. | 2 | | 001-099 |
| 0050 | 20 | | GA | | 5-0 | 26-11-11 | D01594 | | 24 | | GD01649 | ST.. | 2 | | 115-199 |
| 0051 | 20 | | GA | | 85-0 | 28-22-21 | D40014J | | 15 | | TB0059Y | A005 | BJ | | ALL |
| 0052 | 20 | | GA | | 20-0 | 28-22-21 | D40901P | | 3 | | TB0059Y | A005 | BJ | | 001-099 |
| 0052 | 20 | | GA | | 21-0 | 28-22-21 | D40901P | | 3 | | TB0059Y | A005 | BJ | | 115-199 |
| 0054 | 22 | | GA | | 20-0 | 77-12-41 | D41948P | | 30 | | D42004P | | 9 | | ALL |
| 0055 | 20 | | GA | | 68-0 | 26-12-11 | D41944P | | 26 | | D40026J | | 10 | | ALL |
| 0056 | 20 | | GA | | 68-0 | 26-12-11 | D41944P | | 27 | | D40026J | | 11 | | ALL |
| 0057 | 22 | | GA | | 23-0 | 26-12-11 | D41944P | | 28 | | D41738P | | 13 | | 001-099 |
| 0057 | 22 | | GA | | 22-0 | 26-12-11 | D41944P | | 28 | | D41738P | | 13 | | 115-199 |
| 0058 | 22 | | GA | | 28-0 | 26-11-12 | D41944P | | 29 | | D03232 | | 1 | | 001-099 |
| 0058 | 22 | | GA | | 28-0 | 26-12-11 | D41944P | | 29 | | D03232 | | 1 | | 115-199 |
| 0059 | 22 | | GA | | 28-0 | 26-12-11 | D41944P | | 30 | | D03490 | | 1 | | ALL |
| 0060 | 22 | | GA | | 6-0 | 26-12-11 | D03490 | | 2 | | GD01649 | DC.. | 2 | | 001-099 |
| 0060 | 20 | | GA | | 6-0 | 26-12-11 | D03490 | | 2 | | GD01649 | DC.. | 2 | | 115-199 |
| 0061 | 22 | | GA | | 39-0 | 26-21-11 | D03232 | | 2 | | D41738P | | 14 | | 001-099 |
| 0061 | 22 | | GA | | 40-0 | 26-21-11 | D03232 | | 2 | | D41738P | | 14 | | 115-199 |
| 0062 | 20 | | GA | | 21-0 | 26-21-11 | D01594 | | 9 | | D44108P | | 2 | | 001-099 |
| 0062 | 20 | | GA | | 22-0 | 26-21-11 | D01594 | | 9 | | D44108P | | 2 | | 115-199 |
| 0063 | 20 | | GA | | 21-0 | 26-21-11 | D01594 | | 22 | | D44102P | | 1 | | 001-099 |
| 0063 | 20 | | GA | | 22-0 | 26-21-11 | D01594 | | 22 | | D44102P | | 1 | | 115-199 |
| 0064 | 20 | | GA | | 28-0 | 26-21-11 | D01594 | | 23 | | D42006P | | 5 | | ALL |
| 0065 | 20 | | GA | | 5-0 | 26-21-11 | D01594 | | 8 | | SM00009 | | 9 | | 001-099 |
| 0065 | 20 | | GA | | 8-0 | 26-21-11 | D01594 | | 8 | | SM00009 | | 9 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | 286N4228 | | | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | |
| 0066 | 24 | | GK | | 20-0 | 80-11-11 | D42004P | | 3 | | D41948P | | 9 | | ALL |
| 0067 | 20 | | GA | | 20-0 | SPARE | D42004P | | 4 | | D41948P | | 10 | | ALL |
| 0068 | 20 | | GA | | 20-0 | SPARE | D42004P | | 5 | | D41948P | | 11 | | 115-199 |
| 0069Y | 20 | | QB | | 5-0 | 27-41-11 | D40901P | | 2 | | TB0100X | B003 | BJ | | 001-099 |
| 0069Y | 20 | | QB | | 6-0 | 27-41-11 | D40901P | | 2 | | TB0100X | B003 | BJ | | 115-199 |
| 0070Y | 20 | | QB | | 50-0 | 27-41-11 | D40901P | | 18 | | D42026P | | 1 | | ALL |
| 0071Y | 20 | | QB | | 50-0 | 27-41-11 | D40901P | | 19 | | D42026P | | 2 | | ALL |
| 0072 | 20 | | GA | | 23-0 | 28-22-31 | D42006P | | 3 | | D41948P | | 12 | | 001-008 |
| 0072 | 20 | | GA | | 23-0 | SPARE | D42006P | | 3 | | D41948P | | 12 | | 009-099 |
| 0072 | 20 | | GA | | 24-0 | 28-22-31 | D42006P | | 3 | | D41948P | | 12 | | 115-199 |
| 0073 | 20 | | GA | | 6-0 | 36-11-11 | D01594 | | 14 | | TB0058X | D010 | BJ | | 001-099 |
| 0073 | 20 | | GA | | 7-0 | 36-11-11 | D01594 | | 14 | | TB0058X | D010 | BJ | | 115-199 |
| 0074 | 20 | | GA | | 6-0 | 36-11-11 | D01594 | | 31 | | TB0058X | C010 | BJ | | 001-099 |
| 0074 | 20 | | GA | | 7-0 | 36-11-11 | D01594 | | 31 | | TB0058X | C010 | BJ | | 115-199 |
| 0075 | 22 | | GA | | 21-0 | 26-11-11 | D41944P | | 22 | | D41948P | | 38 | | 001-099 |
| 0077 | 24 | | GK | | 23-0 | 21-58-12 | D41948P | | 52 | | SM00003 | | 9 | | 001-099 |
| 0077 | 24 | | GK | | 21-0 | 21-58-12 | SM00003 | | | 9 | D41948P | | 52 | | 115-199 |
| 0078 | 22 | | GA | | 50-0 | 78-34-11 | D42012P | | 21 | | TB0059Y | A006 | BJ | | 001-002 |
| 0078 | 22 | | GA | | 50-0 | 78-34-11 | D42012P | | 9 | | TB0059Y | A006 | BJ | | 003-099 |
| 0078 | 22 | | GA | | 48-0 | 78-34-11 | D42012P | | 23 | | TB0059Y | A006 | BJ | | 115-199 |
| 0079 | 22 | | GA | | 20-0 | 33-16-51 | D01594 | | 1 | | TB0100Y | C010 | BJ | | ALL |
| 0080 | 22 | | GA | | 19-0 | 33-16-51 | D03232 | | 4 | | TB0100Y | A010 | BJ | | 001-099 |
| 0080 | 22 | | GA | | 20-0 | 33-16-51 | D03232 | | 4 | | TB0100Y | A010 | BJ | | 115-199 |
| 0083 | 22 | | GA | | 39-0 | 49-61-11 | D41738P | | 17 | | TB0058X | B011 | BJ | | 001-099 |
| 0083 | 22 | | GA | | 40-0 | 49-61-11 | D41738P | | 17 | | TB0058X | B011 | BJ | | 115-199 |
| 0084 | 22 | | GA | | 39-0 | 49-61-11 | D41738P | | 18 | | TB0058X | C011 | BJ | | 001-099 |
| 0084 | 22 | | GA | | 40-0 | 49-61-11 | D41738P | | 18 | | TB0058X | C011 | BJ | | 115-199 |
| 0085 | 22 | | GA | | 39-0 | 49-61-11 | D41738P | | 19 | | TB0058X | D011 | BJ | | 001-099 |
| 0085 | 22 | | GA | | 40-0 | 49-61-11 | D41738P | | 19 | | TB0058X | D011 | BJ | | 115-199 |
| 0086 | 20 | | GA | | 6-0 | 31-51-33 | D01594 | | 15 | | GD00742 | DC.. | 2 | | 001-099 |
| 0086 | 20 | | GA | | 5-0 | 31-51-33 | D01594 | | 15 | | GD00742 | DC.. | 2 | | 115-199 |
| 0087 | 22 | | GA | | 51-0 | 31-51-33 | D01594 | | 4 | | D42012P | | 6 | | ALL |
| 0088 | 22 | | GA | | 34-0 | 31-51-21 | D41944P | | 32 | | D42012P | | 7 | | 001-099 |
| 0088 | 22 | | GA | | 33-0 | 31-51-21 | D41944P | | 32 | | D42012P | | 7 | | 115-199 |
| 0089 | 22 | | GA | | 34-0 | 31-51-21 | D41944P | | 33 | | D42012P | | 8 | | 001-099 |
| 0089 | 22 | | GA | | 33-0 | 31-51-21 | D41944P | | 33 | | D42012P | | 8 | | 115-199 |
| 0090 | 22 | | GA | | 20-0 | 77-12-41 | D42004P | | 6 | | D41948P | | 13 | | ALL |
| 0091 | 24 | | GK | | 22-0 | 77-12-41 | D42004P | | 7 | | D41738P | | 20 | | 001-099 |
| 0091 | 22 | | GA | | 22-0 | 77-12-41 | D42004P | | 7 | | D41738P | | 20 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | 286N4228 | | | | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | |
| 0092 | 22 | | GA | | 6-0 | 33-16-61 | | D03232 | | 3 | | TB0058Z | 4 | BJ | | 001-099 |
| 0092 | 22 | | GA | | 7-0 | 33-16-61 | | D03232 | | 3 | | TB0058Z | 4 | BJ | | 115-199 |
| 0093 | 22 | | GA | | 65-0 | 29-11-12 | | D41738P | | 21 | | D40002J | 8 | | | 001-099 |
| 0093 | 20 | | GA | | 65-0 | 29-11-12 | | D40002J | | 8 | | D41738P | 21 | | | 115-199 |
| 0094 | 20 | | GA | | 63-0 | SPARE | | D40002J | | 10 | | D41948P | 14 | | | 115-199 |
| 0096 | 22 | | GA | | 64-0 | SPARE | | D41948P | | 11 | | D40014J | 12 | | | 001-099 |
| 0096 | 20 | | GA | | 85-0 | SPARE | | D40014J | | 12 | | D40901P | 8 | | | 115-199 |
| 0097 | 20 | | GA | | 45-0 | SPARE | | D40026J | | 9 | | D42012P | 9 | | | 001-002 |
| 0097 | 20 | | GA | | 44-0 | SPARE | | D40026J | | 9 | | D42012P | 9 | | | 115-199 |
| 0099 | 22 | | GA | | 71-0 | 29-11-11 | | D40014J | | 1 | | D42006P | 22 | | | 001-099 |
| 0099 | 20 | | GA | | 71-0 | 29-11-11 | | D40014J | | 1 | | D42006P | 22 | | | 115-199 |
| 0100 | 22 | | GA | | 86-0 | 29-11-11 | | D40014J | | 9 | | D01594 | 37 | | | 001-099 |
| 0100 | 20 | | GA | | 86-0 | 29-11-11 | | D40014J | | 9 | | D01594 | 37 | | | 115-199 |
| 0101 | 22 | | GA | | 86-0 | 29-11-11 | | D40014J | | 10 | | D01594 | 36 | | | 001-099 |
| 0101 | 20 | | GA | | 86-0 | 29-11-11 | | D40014J | | 10 | | D01594 | 36 | | | 115-199 |
| 0102 | 22 | | GA | | 28-0 | 29-11-11 | | D01594 | | 35 | | D42006P | 20 | | | ALL |
| 0103 | 22 | | GA | | 28-0 | 29-11-11 | | D01594 | | 34 | | D42006P | 21 | | | ALL |
| 0104 | 22 | | GA | | 10-0 | 29-11-12 | | D42006P | | 26 | | SM00002 | | 9 | | 001-099 |
| 0104 | 20 | | GA | | 71-0 | 29-11-12 | | D40002J | | 42 | | D42006P | 26 | | | 115-199 |
| 0105 | 20 | | GA | | 71-0 | SPARE | | D40002J | | 9 | | D42006P | 27 | | | 115-199 |
| 0106 | 22 | | GA | | 67-0 | 29-11-12 | | D40002J | | 42 | | SM00002 | | 9 | | 001-099 |
| 0107 | 22 | | GA | | 21-0 | 29-11-12 | | D41738P | | 22 | | SM00002 | | 9 | | 001-099 |
| 0108 | 22 | | GA | | 68-0 | SPARE | | D40002J | | 21 | | D42004P | 10 | | | 001-099 |
| 0108 | 22 | | GA | | 85-0 | SPARE | | D40002J | | 22 | | D40901P | 6 | | | 115-199 |
| 0109 | 20 | | GA | | 65-0 | SPARE | | D40002J | | 41 | | D41738P | 42 | | | 001-099 |
| 0109 | 22 | | GA | | 85-0 | SPARE | | D40002J | | 41 | | D40901P | 10 | | | 115-199 |
| 0116 | 20 | | GA | | 3-0 | 73-21-11 | | D04162 | | 18 | | GD02168 | DC.. | E | | ALL |
| 0117 | 20 | | GA | | 3-0 | 73-21-11 | | D04162 | | 23 | | GD02169 | ST.. | E | | ALL |
| 0118 | 24 | | GK | | 24-0 | 73-21-11 | | D04162 | | 1 | | D41948P | 29 | | | ALL |
| 0119 | 18 | | GA | | 46-0 | 73-21-11 | | D04162 | | 2 | | TB0116F | C008 | 2 | | 001-099 |
| 0119 | 18 | | GA | | 45-0 | 73-21-11 | | D04162 | | 2 | | TB0158F | C011 | 2 | | 115-199 |
| 0120 | 18 | | GA | | 50-0 | 73-21-12 | | D04160 | | 7 | | D06400 | 18 | 18 | | ALL |
| 0121 | 24 | | GK | | 12-0 | 74-31-11 | | D41948P | | 24 | | D41738P | 23 | | | 001-099 |
| 0121 | 24 | | GK | | 42-0 | 73-21-12 | | D41948P | | 34 | | SM00101 | | 9 | | 115-199 |
| 0122 | 18 | | GA | | 44-0 | 73-21-12 | | D06400 | | 17 | 18 | D41738P | 30 | 18 | | ALL |
| 0123 | 24 | | GK | | 44-0 | 73-21-12 | | D06400 | | 21 | | D41738P | 31 | | | ALL |
| 0124 | 24 | | GK | | 24-0 | 73-21-12 | | D04160 | | 5 | | D41948P | 35 | | | 001-099 |
| 0124 | 24 | | GK | | 24-0 | 73-21-12 | | D41948P | | 35 | | D04160 | 5 | | | 115-199 |
| 0125 | 24 | | GK | | 26-0 | 73-21-12 | | D41738P | | 32 | | D04160 | 36 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | 286N4228 | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | | | |
| 0125 | 24 | | GK | | 26-0 | 73-21-12 | D04160 | | 36 | | D41738P | | 32 | | 115-199 |
| 0126 | 24 | | GK | | 28-0 | 73-21-12 | D42004P | | 16 | | D04160 | | 33 | | 001-099 |
| 0126 | 24 | | GK | | 28-0 | 73-21-12 | D04160 | | 33 | | D42004P | | 16 | | 115-199 |
| 0127 | 24 | | GK | | 28-0 | 73-21-12 | D42004P | | 11 | | D04160 | | 17 | | 001-099 |
| 0127 | 24 | | GK | | 28-0 | 73-21-12 | D04160 | | 17 | | D42004P | | 11 | | 115-199 |
| 0128 | 24 | | GK | | 28-0 | 73-21-12 | D42004P | | 12 | | D04160 | | 34 | | 001-099 |
| 0128 | 24 | | GK | | 28-0 | 73-21-12 | D04160 | | 34 | | D42004P | | 12 | | 115-199 |
| 0129 | 24 | | GK | | 28-0 | 73-21-12 | D42004P | | 13 | | D04160 | | 18 | | 001-099 |
| 0129 | 24 | | GK | | 28-0 | 73-21-12 | D04160 | | 18 | | D42004P | | 13 | | 115-199 |
| 0130 | 24 | | GK | | 28-0 | 73-21-12 | D42004P | | 14 | | D04160 | | 19 | | 001-099 |
| 0130 | 24 | | GK | | 28-0 | 73-21-12 | D04160 | | 19 | | D42004P | | 14 | | 115-199 |
| 0131 | 24 | | GK | | 28-0 | 73-21-12 | D42004P | | 15 | | D04160 | | 35 | | 001-099 |
| 0131 | 24 | | GK | | 28-0 | 73-21-12 | D04160 | | 35 | | D42004P | | 15 | | 115-199 |
| 0132 | 20 | | GA | | 3-0 | 73-21-12 | D04162 | | 19 | | GD02168 | DC.. | E | | ALL |
| 0133 | 16 | | GA | | 67-0 | 75-31-11 | SM00001 | | 9 | | D40014J | | 3 | | 001-099 |
| 0133 | 16 | | GA | | 43-0 | 75-31-11 | SM00001 | | 9 | | D40014J | | 3 | | 115-199 |
| 0134 | 16 | | GA | | 42-0 | 75-31-11 | SM00004 | | 9 | | D40014J | | 17 | | 001-099 |
| 0134 | 16 | | GA | | 47-0 | 75-31-11 | SM00004 | | 9 | | D40014J | | 17 | | 115-199 |
| 0135 | 20 | | GA | | 6-0 | 21-25-11 | D03496 | | 10 | | GD00742 | DC.. | 2 | | 001-099 |
| 0135 | 20 | | GA | | 5-0 | 21-25-11 | D03496 | | 10 | | GD00742 | DC.. | 2 | | 115-199 |
| 0136 | 24 | | GK | | 51-0 | 31-51-33 | D03496 | | 21 | | D42012P | | 10 | | ALL |
| 0137 | 20 | | GA | | 6-0 | 33-13-52 | D03496 | | 1 | | TB0058Z | | 3 | BJ | 001-099 |
| 0137 | 20 | | GA | | 7-0 | 33-13-52 | D03496 | | 1 | | TB0058Z | | 3 | BJ | 115-199 |
| 0138 | 20 | | GA | | 6-0 | 33-13-52 | D03496 | | 2 | | GD00742 | AC.. | 2 | | 001-099 |
| 0138 | 20 | | GA | | 5-0 | 33-13-52 | D03496 | | 2 | | GD00742 | AC.. | 2 | | 115-199 |
| 0139 | 22 | | GA | | 20-0 | 33-16-51 | D03496 | | 3 | | TB0100Y | C005 | BJ | | ALL |
| 0140 | 22 | | GA | | 20-0 | 33-16-51 | D03496 | | 4 | | TB0100Y | C009 | BJ | | ALL |
| 0141 | 20 | | GA | | 23-0 | 28-22-31 | D42006P | | 4 | | D41948P | | 15 | | 001-008 |
| 0141 | 20 | | GA | | 23-0 | SPARE | D42006P | | 4 | | D41948P | | 15 | | 009-099 |
| 0141 | 20 | | GA | | 24-0 | 28-22-31 | D42006P | | 4 | | D41948P | | 15 | | 115-199 |
| 0142 | 22 | | GA | | 28-0 | 29-11-11 | D01594 | | 18 | | D42006P | | 18 | | ALL |
| 0143 | 22 | | GA | | 28-0 | 29-11-11 | D01594 | | 17 | | D42006P | | 19 | | ALL |
| 0144 | 24 | | GK | | 12-0 | 76-11-11 | D41738P | | 44 | | D41948P | | 17 | | ALL |
| 0145 | 24 | | GK | | 12-0 | 76-11-11 | D41738P | | 45 | | D41948P | | 18 | | ALL |
| 0146 | 22 | | GA | | 23-0 | 26-15-11 | D41738P | | 11 | | D41944P | | 41 | | 001-099 |
| 0146 | 22 | | GA | | 22-0 | 26-15-11 | D41738P | | 11 | | D41944P | | 41 | | 115-199 |
| 0147 | 22 | | GA | | 23-0 | 26-15-11 | D41738P | | 12 | | D41944P | | 42 | | 001-099 |
| 0147 | 22 | | GA | | 22-0 | 26-15-11 | D41738P | | 12 | | D41944P | | 42 | | 115-199 |
| 0148 | 22 | | GA | | 21-0 | 26-15-11 | D41948P | | 21 | | D41944P | | 21 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | 286N4228 | | | | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | |
| 0149 | 22 | | GA | | 29-0 | SPARE | | D42012P | | 11 | | D41948P | | 19 | | 001-099 |
| 0149 | 22 | | GA | | 21-0 | SPARE | | D41944P | | 43 | | D41948P | | 19 | | 115-199 |
| 0150 | 22 | | GA | | 21-0 | SPARE | | D41944P | | 44 | | D41948P | | 20 | | 115-199 |
| 0151 | 22 | | GA | | 21-0 | SPARE | | D41944P | | 45 | | D41948P | | 22 | | 115-199 |
| 0152 | 22 | | GA | | 21-0 | SPARE | | D41944P | | 46 | | D41948P | | 23 | | ALL |
| 0153 | 22 | | GA | | 27-0 | 26-16-11 | | D41944P | | 47 | | D03496 | | 12 | | 001-099 |
| 0153 | 22 | | GA | | 28-0 | 26-16-11 | | D41944P | | 47 | | D03496 | | 12 | | 115-199 |
| 0154 | 22 | | GA | | 13-0 | SPARE | | D41944P | | 23 | | D42006P | | 10 | | ALL |
| 0155 | 22 | | GA | | 23-0 | 26-16-11 | | D41944P | | 39 | | D41738P | | 46 | | 001-099 |
| 0155 | 22 | | GA | | 22-0 | 26-16-11 | | D41944P | | 39 | | D41738P | | 46 | | 115-199 |
| 0156 | 22 | | GA | | 23-0 | 26-16-11 | | D41944P | | 40 | | D41738P | | 47 | | 001-099 |
| 0156 | 22 | | GA | | 22-0 | 26-16-11 | | D41944P | | 40 | | D41738P | | 47 | | 115-199 |
| 0157 | 22 | | GA | | 22-0 | 26-22-21 | | D41944P | | 17 | | D41738P | | 43 | | 115-199 |
| 0158 | 20 | | GA | | 21-0 | 26-22-21 | | D41944P | | 48 | | D41948P | | 24 | | 115-199 |
| 0159 | 20 | | GA | | 21-0 | 26-22-21 | | D41944P | | 49 | | D41948P | | 26 | | 115-199 |
| 0160 | 20 | | GA | | 24-0 | 26-22-21 | | D42006P | | 9 | | D41948P | | 25 | | 115-199 |
| 0161 | 22 | | GA | | 23-0 | 26-23-11 | | D41738P | | 48 | | D41944P | | 50 | | 001-099 |
| 0161 | 22 | | GA | | 22-0 | 26-23-11 | | D41738P | | 48 | | D41944P | | 50 | | 115-199 |
| 0162 | 22 | | GA | | 23-0 | 26-23-11 | | D41738P | | 49 | | D41944P | | 51 | | 001-099 |
| 0162 | 22 | | GA | | 22-0 | 26-23-11 | | D41738P | | 49 | | D41944P | | 51 | | 115-199 |
| 0163 | 20 | | GA | | 28-0 | 26-23-11 | | D03496 | | 15 | | D41944P | | 52 | | ALL |
| 0164 | 20 | | GA | | 6-0 | 26-23-11 | | D03496 | | 23 | | GD01649 | DC.. | 2 | | 001-099 |
| 0164 | 20 | | GA | | 5-0 | 26-23-11 | | D03496 | | 23 | | GD01649 | DC.. | 2 | | 115-199 |
| 0165 | 20 | | GA | | 28-0 | 26-23-11 | | D03496 | | 22 | | D41944P | | 53 | | ALL |
| 0166 | 20 | | GA | | 28-0 | 26-23-11 | | D03496 | | 5 | | D41944P | | 54 | | ALL |
| 0167 | 20 | | GA | | 21-0 | 26-23-11 | | D03496 | | 16 | | D44108P | | 3 | | 001-099 |
| 0167 | 20 | | GA | | 22-0 | 26-23-11 | | D03496 | | 16 | | D44108P | | 3 | | 115-199 |
| 0168 | 20 | | GA | | 21-0 | 26-23-11 | | D03496 | | 20 | | D44102P | | 2 | | 001-099 |
| 0168 | 20 | | GA | | 22-0 | 26-23-11 | | D03496 | | 20 | | D44102P | | 2 | | 115-199 |
| 0169 | 20 | | GA | | 21-0 | 26-23-11 | | D03496 | | 17 | | D44102P | | 3 | | 001-099 |
| 0169 | 20 | | GA | | 22-0 | 26-23-11 | | D03496 | | 17 | | D44102P | | 3 | | 115-199 |
| 0170 | 20 | | GA | | 25-0 | 26-21-11 | | SM00009 | | 9 | | D41944P | | 34 | | 001-099 |
| 0170 | 20 | | GA | | 21-0 | 26-21-11 | | SM00009 | | 9 | | D41944P | | 34 | | 115-199 |
| 0171 | 20 | | GA | | 13-0 | 26-21-11 | | D42006P | | 8 | | D41944P | | 55 | | ALL |
| 0172 | 22 | | GA | | 23-0 | 26-21-11 | | D41738P | | 15 | | D41944P | | 35 | | 001-099 |
| 0172 | 22 | | GA | | 22-0 | 26-21-11 | | D41738P | | 15 | | D41944P | | 35 | | 115-199 |
| 0174 | 22 | | GA | | 25-0 | SPARE | | D42006P | | 11 | | D42004P | | 8 | | 001-099 |
| 0174 | 22 | | GA | | 25-0 | 29-22-11 | | D42006P | | 11 | | D42004P | | 8 | | 115-199 |
| 0175 | 22 | | GA | | 29-0 | 32-42-11 | | D41948P | | 28 | | D42012P | | 18 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | 286N4228 | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | | | |
| 0175 | 22 | GA | | | 27-0 | 32-42-11 | D41948P | 28 | | | D42012P | 18 | | | 115-199 |
| 0176 | 24 | GK | | | 6-0 | 21-43-11 | D03496 | 8 | | | TB0059X | C010 | BJ | | ALL |
| 0177 | 24 | GK | | | 6-0 | 21-43-11 | D03496 | 6 | | | TB0059X | D010 | BJ | | ALL |
| 0179 | 22 | GA | | | 65-0 | 29-11-12 | D40002J | 12 | | | D41738P | 24 | | | 001-099 |
| 0179 | 20 | GA | | | 65-0 | 29-11-12 | D40002J | 12 | | | D41738P | 24 | | | 115-199 |
| 0180 | 24 | GK | | | 6-0 | 36-11-41 | D01594 | 3 | | | TB0058X | D012 | BJ | | 001-099 |
| 0180 | 24 | GK | | | 7-0 | 36-11-41 | D01594 | 3 | | | TB0058X | D012 | BJ | | 115-199 |
| 0181 | 24 | GK | | | 6-0 | 36-11-41 | D01594 | 12 | | | TB0058X | D001 | BJ | | 001-099 |
| 0181 | 24 | GK | | | 7-0 | 36-11-41 | D01594 | 12 | | | TB0058X | D001 | BJ | | 115-199 |
| 0185 | 22 | GA | | | 6-0 | 24-22-11 | D01594 | 21 | | | TB0058X | C007 | BJ | | 001-099 |
| 0185 | 22 | GA | | | 7-0 | 24-22-11 | D01594 | 21 | | | TB0058X | C007 | BJ | | 115-199 |
| 0186 | 22 | GA | | | 6-0 | 24-22-11 | D01594 | 40 | | | TB0058X | D007 | BJ | | 001-099 |
| 0186 | 22 | GA | | | 7-0 | 24-22-11 | D01594 | 40 | | | TB0058X | D007 | BJ | | 115-199 |
| 0187 | 22 | GA | | | 1-0 | 26-11-11 | TB0158A | C009 | 2 | | TB0158A | C008 | 2 | | ALL |
| 0188 | 22 | GA | | | 20-0 | 26-11-11 | D40901P | 1 | | | TB0158A | A005 | 2 | | 001-099 |
| 0188 | 22 | GA | | | 21-0 | 26-11-11 | D40901P | 1 | | | TB0158A | A005 | 2 | | 115-199 |
| 0190 | 20 | GA | | | 1-0 | 73-21-12 | D04734 | | | AE | GD02900 | ST.. | E | | 001-099 |
| 0190 | 20 | GA | | | 4-0 | 73-21-12 | D04734 | | | AE | GD01975 | ST.. | E | | 115-199 |
| 0191 | 16 | GA | | | 27-0 | 75-31-11 | D04162 | 16 | | | SM00001 | | 9 | | 001-099 |
| 0191 | 16 | GA | | | 5-0 | 75-31-11 | D04162 | 16 | | | SM00001 | | 9 | | 115-199 |
| 0192 | 16 | GA | | | 27-0 | 75-31-11 | SP01048 | | 9 | | SM00001 | | 9 | | 001-099 |
| 0192 | 16 | GA | | | 5-0 | 75-31-11 | SP01048 | | 9 | | SM00001 | | 9 | | 115-199 |
| 0193 | 16 | GA | | | 23-0 | 75-31-11 | SP01046 | | 9 | | D41948P | 40 | 16 | | 001-099 |
| 0193 | 16 | GA | | | 24-0 | 75-31-11 | SP01046 | | 9 | | D41948P | 40 | 16 | | 115-199 |
| 0194 | 22 | GA | | | 23-0 | SPARE | D41948P | 27 | | | D42006P | 12 | | | 001-099 |
| 0194 | 22 | GA | | | 24-0 | SPARE | D41948P | 27 | | | D42006P | 12 | | | 115-199 |
| 0195 | 22 | GA | | | 23-0 | SPARE | D42006P | 13 | | | D41948P | 33 | | | 001-099 |
| 0195 | 22 | GA | | | 24-0 | 32-44-11 | D42006P | 13 | | | D41948P | 33 | | | 115-199 |
| 0196 | 22 | GA | | | 63-0 | 29-22-11 | D40002J | 53 | | | D41948P | 53 | | | ALL |
| 0197 | 22 | GA | | | 63-0 | 29-22-11 | D40002J | 54 | | | D41948P | 54 | | | ALL |
| 0198 | 22 | GA | | | 63-0 | 29-22-11 | D40002J | 55 | | | D41948P | 55 | | | ALL |
| 0200 | 20 | GA | | | 37-0 | 28-21-11 | D42012P | 15 | | | D42006P | 15 | | | 001-099 |
| 0200 | 22 | GA | | | 35-0 | 28-21-11 | D42012P | 15 | | | D42006P | 15 | | | 115-199 |
| 0201 | 22 | GA | | | 71-0 | SPARE | D40002J | 13 | | | D42006P | 14 | | | 001-099 |
| 0201 | 20 | GA | | | 71-0 | 28-41-21 | D40002J | 13 | | | D42006P | 14 | | | 115-199 |
| 0202 | 20 | GA | | | 45-0 | 28-25-11 | D40002J | 14 | | | D42012P | 14 | | | 001-099 |
| 0202 | 20 | GA | | | 44-0 | 28-25-11 | D42012P | 14 | | | D40002J | 14 | | | 115-199 |
| 0208 | 20 | GA | | | 37-0 | 32-35-11 | D42012P | 16 | | | D42006P | 23 | | | 001-099 |
| 0208 | 20 | GA | | | 34-0 | 32-35-11 | D42012P | 16 | | | D42006P | 23 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|---|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W4228 | 286N4228 | | | | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | |
| 0209 | 20 | | GA | | 37-0 | 32-35-11 | D42012P | | 17 | | | D42006P | 24 | | | 001-099 |
| 0209 | 20 | | GA | | 34-0 | 32-35-11 | D42012P | | 17 | | | D42006P | 24 | | | 115-199 |
| 0210 | 22 | | GA | | 63-0 | 29-22-11 | D40002J | | 35 | | | D41948P | 42 | | | 001-099 |
| 0210 | 22 | | GA | | 71-0 | 29-22-11 | D40002J | | 35 | | | D42006P | 25 | | | 115-199 |
| 0212 | 16 | | GA | | 7-0 | 75-31-11 | D04162 | | 15 | | | SM00004 | | 9 | | 001-099 |
| 0212 | 16 | | GA | | 1-0 | 75-31-11 | D04162 | | 15 | | | SM00004 | | 9 | | 115-199 |
| 0213 | 16 | | GA | | 7-0 | 75-31-11 | SP01050 | | | 9 | | SM00004 | | 9 | | 001-099 |
| 0213 | 16 | | GA | | 5-0 | 75-31-11 | SP01050 | | | 9 | | SM00004 | | 9 | | 115-199 |
| 0214 | 22 | | GA | | 63-0 | 76-11-11 | D41248P | | 3 | | | D40002J | 20 | | | ALL |
| 0215 | 24 | | GK | | 37-0 | 73-21-11 | D41948P | | 31 | | | TB0158X | B004 | BJ | | 001-099 |
| 0215 | 24 | | GK | | 38-0 | 73-21-11 | D41948P | | 31 | | | TB0158X | B004 | BJ | | 115-199 |
| 0216 | 24 | | GK | | 18-0 | 73-21-12 | D42230P | | 12 | | | D41948P | 36 | | | 001-099 |
| 0216 | 24 | | GK | | 19-0 | 73-21-12 | D41948P | | 36 | | | D42230P | 12 | | | 115-199 |
| 0217 | 24 | | GK | | 42-0 | 73-21-12 | D06400 | | 19 | | | D41948P | 37 | | | 001-099 |
| 0217 | 24 | | GK | | 42-0 | 73-21-12 | D41948P | | 37 | | | D06400 | 19 | | | 115-199 |
| 0218 | 24 | | GK | | 42-0 | 73-21-12 | D06400 | | 22 | | | D41948P | 44 | | | 001-099 |
| 0218 | 24 | | GK | | 42-0 | 73-21-12 | D41948P | | 38 | | | D06400 | 22 | | | 115-199 |
| 0219 | 24 | | GK | | 20-0 | 73-21-12 | D42230P | | 11 | | | D41738P | 25 | | | 001-099 |
| 0219 | 24 | | GK | | 21-0 | 73-21-12 | D42230P | | 11 | | | D41738P | 25 | | | 115-199 |
| 0220 | 20 | | GA | | 63-0 | 36-11-11 | D40026J | | 7 | | | D41948P | 8 | | | 001-099 |
| 0220 | 20 | | GA | | 64-0 | 36-11-11 | D40026J | | 7 | | | D41948P | 8 | | | 115-199 |
| 0221 | 22 | | GA | | 26-0 | 29-11-12 | D41738P | | 22 | | | D42006P | 28 | | | 115-199 |
| 0222 | 22 | | GA | | 26-0 | 29-11-12 | D41738P | | 23 | | | D42006P | 29 | | | 115-199 |
| 0224 | 22 | | GA | | 63-0 | 76-11-11 | D41248P | | 4 | | | D40014J | 7 | | | ALL |
| 0226 | 22 | | GA | | 36-0 | 76-11-11 | D40901P | | 13 | | | D41248P | 2 | | | 001-099 |
| 0226 | 22 | | GA | | 37-0 | 76-11-11 | D40901P | | 13 | | | D41248P | 2 | | | 115-199 |
| 0227 | 20 | | GA | | 17-0 | 26-21-11 | D44102P | | 4 | | | SM00009 | | 9 | | 001-099 |
| 0227 | 20 | | GA | | 16-0 | 26-21-11 | D44102P | | 4 | | | SM00009 | | 9 | | 115-199 |
| 0228 | 22 | | GA | | 37-0 | 76-11-11 | D01594 | | 6 | | | D41248P | 1 | | | 001-099 |
| 0228 | 22 | | GA | | 38-0 | 76-11-11 | D01594 | | 6 | | | D41248P | 1 | | | 115-199 |
| 0230 | 24 | | GK | | 5-0 | 21-58-12 | D05632 | | 4 | | | SM00005 | | 9 | | ALL |
| 0231 | 20 | | GA | | 4-0 | 21-58-12 | D05632 | | 5 | | | GD03626 | DC.. | E | | ALL |
| 0232 | 24 | | GK | | 5-0 | 21-58-12 | D05632 | | 12 | | | SM00003 | | 9 | | ALL |
| 0233 | 20 | | GA | | 4-0 | 21-58-12 | D05632 | | 10 | | | GD00869 | ST.. | E | * | ALL |
| 0234 | 20 | | GA | | 4-0 | 21-58-12 | D05632 | | 11 | | | GD03626 | DC.. | E | | ALL |
| 0235 | 24 | | GK | | 5-0 | 21-58-12 | D05632 | | 9 | | | SM00006 | | 9 | | ALL |
| 0236 | 24 | | GK | | 8-0 | 21-58-12 | D05634 | | 4 | | | SM00005 | | 9 | | ALL |
| 0237 | 20 | | GA | | 3-0 | 21-58-12 | D05634 | | 5 | | | GD03626 | DC.. | E | | ALL |
| 0238 | 24 | | GK | | 8-0 | 21-58-12 | D05634 | | 12 | | | SM00003 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | 286N4228 | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | | | |
| 0239 | 20 | GA | | | 3-0 | 21-58-12 | D05634 | | 10 | | GD00869 | ST.. | E | * | ALL |
| 0240 | 20 | GA | | | 3-0 | 21-58-12 | D05634 | | 11 | | GD03626 | DC.. | E | | ALL |
| 0241 | 24 | GK | | | 8-0 | 21-58-12 | D05634 | | 9 | | SM00007 | | 9 | | ALL |
| 0243 | 24 | GK | | | 25-0 | 21-58-12 | D41738P | | 51 | | SM00006 | | 9 | | 001-099 |
| 0243 | 24 | GK | | | 23-0 | 21-58-12 | D41738P | | 51 | | SM00006 | | 9 | | 115-199 |
| 0244 | 24 | GK | | | 25-0 | 21-58-12 | D41738P | | 52 | | SM00007 | | 9 | | 001-099 |
| 0244 | 24 | GK | | | 23-0 | 21-58-12 | D41738P | | 52 | | SM00007 | | 9 | | 115-199 |
| 0245 | 24 | GK | | | 23-0 | 21-58-12 | D41948P | | 41 | | SM00005 | | 9 | | 001-099 |
| 0245 | 24 | GK | | | 21-0 | 21-58-12 | D41948P | | 41 | | SM00005 | | 9 | | 115-199 |
| 0246 | 24 | GK | | | 23-0 | 21-58-12 | D41948P | | 45 | | SM00006 | | 9 | | 001-099 |
| 0246 | 24 | GK | | | 21-0 | 21-58-12 | D41948P | | 45 | | SM00006 | | 9 | | 115-199 |
| 0247 | 24 | GK | | | 23-0 | 21-58-12 | D41948P | | 47 | | SM00007 | | 9 | | 001-099 |
| 0247 | 24 | GK | | | 21-0 | 21-58-12 | D41948P | | 47 | | SM00007 | | 9 | | 115-199 |
| 0248 | 18 | GA | | | 37-0 | 32-12-12 | D42012P | | 20 | 18 | D42006P | | 16 | 18 | 001-099 |
| 0249 | 18 | GA | | | 37-0 | 32-12-12 | D42012P | | 22 | 18 | D42006P | | 31 | 18 | 001-099 |
| 0250 | 20 | GA | | | 29-0 | 32-35-11 | D42012P | | 19 | | D41948P | | 16 | | 001-099 |
| 0251 | 22 | GA | | | 37-0 | 76-11-11 | D40901P | | 21 | | D41948P | | 39 | | 001-099 |
| 0251 | 20 | GA | | | 27-0 | 32-35-11 | D42012P | | 19 | | D41948P | | 16 | | 115-199 |
| 0252 | 22 | GA | | | 23-0 | 26-11-12 | D41944P | | 17 | | D41738P | | 16 | | 001-099 |
| 0252 | 18 | GA | | | 35-0 | 32-12-12 | D42012P | | 20 | 18 | D42006P | | 16 | 18 | 115-199 |
| 0253 | 24 | GK | | | 41-0 | 73-21-12 | D41948P | | 34 | | SM00101 | | 9 | | 001-099 |
| 0253 | 18 | GA | | | 35-0 | 32-12-12 | D42012P | | 21 | 18 | D42006P | | 17 | 18 | 115-199 |
| 0254 | 18 | GA | | | 24-0 | 73-21-12 | D04162 | | 17 | | D41948P | | 43 | 18 | 001-099 |
| 0254 | 18 | GA | | | 24-0 | 73-21-12 | D04162 | | 17 | | D41948P | | 42 | 18 | 115-199 |
| 0255 | 16 | GA | | | 26-0 | 75-31-11 | D42230P | | 14 | 16 | SP01262 | | 9 | | ALL |
| 0256 | 16 | GA | | | 25-0 | 75-31-11 | D42230P | | 15 | 16 | SM00004 | | 9 | | 001-099 |
| 0256 | 16 | GA | | | 26-0 | 75-31-11 | D42230P | | 15 | 16 | SM00004 | | 9 | | 115-199 |
| 0257 | 20 | GA | | | 1-0 | 77-21-11 | D04164 | | 3 | | D04164 | | 4 | | ALL |
| 0258 | 20 | GA | | | 45-0 | SPARE | D40002J | | 30 | | D42012P | | 13 | | 001-099 |
| 0259 | 22 | GA | | | 84-0 | 30-11-11 | D40002J | | 46 | | TB0100X | B002 | BJ | | 001-099 |
| 0259 | 22 | GA | | | 83-0 | 30-11-11 | D40002J | | 46 | | TB0100X | B002 | BJ | | 115-199 |
| 0260 | 22 | GA | | | 84-0 | 30-11-11 | D40002J | | 47 | | TB0100X | A002 | BJ | | 001-099 |
| 0260 | 22 | GA | | | 83-0 | 30-11-11 | D40002J | | 47 | | TB0100X | A002 | BJ | | 115-199 |
| 0261 | 22 | GA | | | 68-0 | 30-11-11 | D40002J | | 48 | | D42004P | | 23 | | ALL |
| 0266 | 24 | GK | | | 1-0 | 73-21-12 | D06400 | | 16 | | SM00101 | | 9 | | ALL |
| 0272 | 22 | GA | | | 9-0 | 33-13-32 | D06400 | | 1 | | TB0116Z | | 22 | BJ | 001-099 |
| 0272 | 22 | GA | | | 8-0 | 33-13-32 | D06400 | | 1 | | TB0115Z | | 13 | BJ | 115-199 |
| 0273 | 22 | GA | | | 8-0 | 33-13-32 | D06400 | | 2 | | TB0115Z | | 14 | BJ | ALL |
| 0274 | 24 | GK | | | 1-0 | 73-21-12 | D06400 | | 23 | | SM00101 | | 9 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 19

Oct 09/2008



WIRE LIST
D280N032

91-21-11
Section W4220
Page 20
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | Effectivity | | | |
|------------|-------------|----|-------|---|------|----------|---------|-------|------|------|--------|---------|-------------|------|------|---------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | | Term | Type | Splice |
| W4228 | 286N4228 | | | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | | |
| 2505Z | | | | AG | 0-0 | 73-21-12 | D04160 | | | | AA | D42230P | 8 | | | 115-199 |
| 2506B | 22 | | GU | CB | 26-0 | 73-21-12 | D42230P | 6 | | | | D04160 | 12 | | | 001-099 |
| 2506B | 24 | | G2 | AM | 27-0 | 73-21-12 | D04160 | 12 | | | | D42230P | 6 | | | 115-199 |
| 2506R | 22 | | GU | CB | 0-0 | 73-21-12 | D42230P | 7 | | | | D04160 | 4 | | | 001-099 |
| 2506R | 24 | | G2 | AM | 0-0 | 73-21-12 | D04160 | 4 | | | | D42230P | 7 | | | 115-199 |
| 2506Z | | | | CB | 0-0 | 73-21-12 | D42230P | 3 | | | | D04160 | | | AA | 001-099 |
| 2506Z | | | | AM | 0-0 | 73-21-12 | D04160 | | | | AA | D42230P | 3 | | | 115-199 |
| 2507B | 22 | | GU | AI | 47-0 | 73-21-12 | D04734 | 1 | | | | D04160 | 40 | | | 001-099 |
| 2507B | 24 | | G2 | AK | 26-0 | 77-12-11 | D04162 | 27 | | | | D41738P | 40 | | | 115-199 |
| 2507R | 22 | | GU | AI | 0-0 | 73-21-12 | D04734 | 2 | | | | D04160 | 41 | | | 001-099 |
| 2507R | 24 | | G2 | AK | 0-0 | 77-12-11 | D04162 | 26 | | | | D41738P | 39 | | | 115-199 |
| 2507Z | | | | AI | 0-0 | 73-21-12 | D04734 | | | | AE | D04160 | 42 | | | 001-099 |
| 2507Z | | | | AK | 0-0 | 77-12-11 | D04162 | DED | | | | D41738P | 41 | | | 115-199 |
| 2508B | 24 | | G2 | AK | 25-0 | 77-12-11 | D41738P | 40 | | | | D04162 | 27 | | | 001-099 |
| 2508R | 24 | | G2 | AK | 0-0 | 77-12-11 | D41738P | 39 | | | | D04162 | 26 | | | 001-099 |
| 2508Z | | | | AK | 0-0 | 77-12-11 | D41738P | 41 | | | | D04162 | DED | | | 001-099 |
| 2509B | 20 | | GU | CC | 68-0 | SPARE | D40002J | 23 | | | | D41944P | 43 | | | 001-099 |
| 2509R | 20 | | GU | CC | 0-0 | SPARE | D40002J | 24 | | | | D41944P | 44 | | | 001-099 |
| 2509Z | | | | CC | 0-0 | SPARE | D40002J | 25 | | | | D41944P | 45 | | | 001-099 |
| 2510B | 20 | | GU | CD | 63-0 | SPARE | D40002J | 26 | | | | D41948P | 48 | | | 001-099 |
| 2510R | 20 | | GU | CD | 0-0 | SPARE | D40002J | 27 | | | | D41948P | 25 | | | 001-099 |
| 2510Z | | | | CD | 0-0 | SPARE | D40002J | 28 | | | | D41948P | 26 | | | 001-099 |
| 3501B | 22 | | GV | BA | 47-0 | 73-21-12 | D04734 | 4 | | | | D04160 | 11 | | | 001-099 |
| 3501B | 22 | | GV | AF | 47-0 | 73-21-12 | D04160 | 11 | | | | D04734 | 4 | | | 115-199 |
| 3501R | 22 | | GV | BA | 0-0 | 73-21-12 | D04734 | 5 | | | | D04160 | 10 | | | 001-099 |
| 3501R | 22 | | GV | AF | 0-0 | 73-21-12 | D04160 | 10 | | | | D04734 | 5 | | | 115-199 |
| 3501Y | 22 | | GV | BA | 0-0 | 73-21-12 | D04734 | 3 | | | | D04160 | 24 | | | 001-099 |
| 3501Y | 22 | | GV | AF | 0-0 | 73-21-12 | D04160 | 24 | | | | D04734 | 3 | | | 115-199 |
| 3501Z | | | | BA | 0-0 | 73-21-12 | D04734 | | | | AE | D04160 | 22 | | | 001-099 |
| 3501Z | | | | AF | 0-0 | 73-21-12 | D04160 | 22 | | | | D04734 | | | AE | 115-199 |
| 4501G | 20 | | DU | AH | 46-0 | 75-31-11 | D04164 | 6 | 4H | | | D40002J | 33 | TC | | 001-099 |
| 4501G | 20 | | DU | AH | 47-0 | 75-31-11 | D04164 | 6 | 4H | | | D40002J | 33 | TC | | 115-199 |
| 4501W | 20 | | DU | AH | 0-0 | 75-31-11 | D04164 | 5 | 4L | | | D40002J | 34 | TD | | ALL |
| 4501Z | | | | AH | 0-0 | 75-31-11 | D04164 | 7 | | | | D40002J | S/R | | | ALL |
| 4502G | 20 | | DU | AL | 46-0 | 77-21-11 | D40002J | 3 | TC | | | D04164 | CAP | Y | | 001-099 |
| 4502G | 20 | | DU | AL | 47-0 | 77-21-11 | D40002J | 3 | TC | | | D04164 | CAP | Y | | 115-199 |
| 4502W | 20 | | DU | AL | 0-0 | 77-21-11 | D40002J | 4 | TD | | | D04164 | CAP | Y | | ALL |
| 4502Z | | | | AL | 0-0 | 77-21-11 | D40002J | S/R | | | | D04164 | DED | | | ALL |
| 5001B | 24 | | G2 | CA | 26-0 | 77-11-11 | D41738P | 33 | | | | D04160 | 14 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4228 | 286N4228 | | | E/E SHELF DISC TO LEFT WING BODY DISC (continued) | | | | | | | | | | | |
| 5001B | 24 | G2 | AN | | 26-0 | 77-11-11 | D04160 | 14 | | | D41738P | 33 | | | 115-199 |
| 5001R | 24 | G2 | CA | | 0-0 | 77-11-11 | D41738P | 34 | | | D04160 | 13 | | | 001-099 |
| 5001R | 24 | G2 | AN | | 0-0 | 77-11-11 | D04160 | 13 | | | D41738P | 34 | | | 115-199 |
| 5001Z | | | CA | | 0-0 | 77-11-11 | D41738P | 35 | | | D04160 | | | AA | 001-099 |
| 5001Z | | | AN | | 0-0 | 77-11-11 | D04160 | | | AA | D41738P | 35 | | | 115-199 |
| 5002B | 24 | G2 | AJ | | 26-0 | 77-11-11 | D41738P | 37 | | | D04162 | 11 | | | 001-099 |
| 5002B | 24 | G2 | AJ | | 26-0 | 77-11-11 | D04162 | 11 | | | D41738P | 37 | | | 115-199 |
| 5002R | 24 | G2 | AJ | | 0-0 | 77-11-11 | D41738P | 36 | | | D04162 | 3 | | | 001-099 |
| 5002R | 24 | G2 | AJ | | 0-0 | 77-11-11 | D04162 | 3 | | | D41738P | 36 | | | 115-199 |
| 5002Z | | | AJ | | 0-0 | 77-11-11 | D41738P | 38 | | | D04162 | 8 | | | 001-099 |
| 5002Z | | | AJ | | 0-0 | 77-11-11 | D04162 | 8 | | | D41738P | 38 | | | 115-199 |
| 5003B | 20 | GU | AP | | 13-0 | 31-31-44 | D42012P | 12 | | | D04160 | 30 | | | 001-099 |
| 5003B | 24 | G2 | AP | | 11-0 | 31-31-23 | D42012P | 12 | | | D04160 | 30 | | | 115-199 |
| 5003R | 20 | GU | AP | | 0-0 | 31-31-44 | D42012P | 23 | | | D04160 | 29 | | | 001-099 |
| 5003R | 24 | G2 | AP | | 0-0 | 31-31-23 | D42012P | 11 | | | D04160 | 29 | | | 115-199 |
| 5003Z | | | AP | | 0-0 | 31-31-44 | D42012P | 24 | | | D04160 | | | AA | 001-099 |
| 5003Z | | | AP | | 0-0 | 31-31-23 | D42012P | 13 | | | D04160 | | | AA | 115-199 |
| A-A | | | | | 0-0 | 75-31-11 | S10379 | 1 | | | SP01046 | 9 | | | ALL |
| A-B | | | | | 0-0 | 75-31-11 | S10379 | 4 | | | SP01046 | 9 | | | ALL |
| A-C | | | | | 0-0 | 75-31-11 | S10379 | 3 | | | SP01048 | 9 | | | ALL |
| A-D | | | | | 0-0 | 75-31-11 | S10379 | 5 | | | SP01050 | CAP | Y | | ALL |
| A-E | | | | | 0-0 | 75-31-11 | S10379 | 7 | | | SP01262 | 9 | | | ALL |
| A-F | | | | | 0-0 | 75-31-11 | S10379 | 8 | | | GD03120 | DC.. | E | | ALL |
| A-G | | | | | 0-0 | 75-31-11 | S10379 | 6 | | | SP01050 | 9 | | | ALL |
| A-H | | | | | 0-0 | 75-31-11 | S10379 | 2 | | | SP01046 | CAP | Y | | ALL |
| FRAA | | | | | 0-0 | 73-21-12 | D04160 | 3 | | | D04160 | | | AA | ALL |
| FRAC | | | | | 0-0 | 73-21-11 | D40002J | | | AC | D40002J | 45 | | | ALL |
| FRAD | | | | | 0-0 | 73-21-11 | D04162 | 20 | | | D04162 | | | AD | ALL |
| FRAT | | | | | 0-0 | 78-34-51 | D41948P | | | AT | D41948P | 49 | | | ALL |
| YAAA | | | | | 0-0 | 76-11-11 | D40014J | S/R | | | GD03041 | ST.. | E | * | 001-099 |
| YAAA | | | | | 0-0 | 29-11-12 | GD03041 | ST.. | E | | D40002J | S/R | | | 115-199 |
| YAAB | | | | | 0-0 | 29-11-12 | D40002J | S/R | | | GD03041 | ST.. | E | * | 001-099 |
| YAAB | | | | | 0-0 | 29-11-11 | GD03041 | ST.. | E | | D40014J | S/R | | | 115-199 |
| YAAC | | | | | 0-0 | 26-11-12 | D40026J | S/R | | | GD03041 | ST.. | E | * | 001-099 |
| YAAC | | | | | 0-0 | 78-34-11 | GD03041 | ST.. | E | | D40026J | S/R | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4220

Page 22 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4230 | 286N4230 | | | E/E SHELF DISC TO LEFT WING BODY DISC- | | | | | | | | | | | |
| 0001 | 22 | GA | | | 68-0 | 73-33-11 | D41354J | | 1 | | D41764P | | 1 | | 001-099 |
| 0001 | 22 | GA | | | 67-0 | 73-33-11 | D41354J | | 1 | | D41764P | | 1 | | 115-199 |
| 0002 | 22 | GA | | | 68-0 | 73-34-11 | D41354J | | 21 | | D41764P | | 2 | | 001-099 |
| 0002 | 22 | GA | | | 67-0 | 73-34-11 | D41354J | | 21 | | D41764P | | 2 | | 115-199 |
| 0003 | 22 | GA | | | 68-0 | 79-33-11 | D41354J | | 10 | | D41764P | | 9 | | 001-099 |
| 0003 | 22 | GA | | | 67-0 | 79-33-11 | D41354J | | 10 | | D41764P | | 9 | | 115-199 |
| 0004 | 22 | GA | | | 68-0 | SPARE | D41354J | | 20 | | D41764P | | 10 | | 001-099 |
| 0005 | 22 | GA | | | 68-0 | 79-35-11 | D41354J | | 11 | | D41764P | | 14 | | 001-099 |
| 0005 | 22 | GA | | | 67-0 | 79-35-11 | D41354J | | 11 | | D41764P | | 14 | | 115-199 |
| 0006R | 20 | QA | | | 67-0 | 26-11-11 | D41354J | | 33 | | D41936P | | 1 | | 001-099 |
| 0006R | 20 | QA | | | 66-0 | 26-11-11 | D41354J | | 33 | | D41936P | | 1 | | 115-199 |
| 0007R | 20 | QA | | | 67-0 | 26-11-11 | D41354J | | 25 | | D41936P | | 10 | | 001-099 |
| 0007R | 20 | QA | | | 66-0 | 26-11-11 | D41354J | | 25 | | D41936P | | 10 | | 115-199 |
| 0008R | 20 | QA | | | 67-0 | 26-11-11 | D41354J | | 27 | | D41936P | | 13 | | 001-099 |
| 0008R | 20 | QA | | | 66-0 | 26-11-11 | D41354J | | 27 | | D41936P | | 13 | | 115-199 |
| 0009 | 22 | GA | | | 31-0 | 26-11-11 | D41936P | | 15 | | TB0112A | C024 | 2 | | 001-099 |
| 0009 | 22 | GA | | | 22-0 | 26-11-11 | D41936P | | 15 | | D41938P | | 15 | | 115-199 |
| 0010 | 22 | GA | | | 23-0 | 26-13-11 | D41764P | | 16 | | D41936P | | 5 | | ALL |
| 0011 | 20 | GA | | | 67-0 | 26-13-11 | D41354J | | 28 | | D41936P | | 3 | | 001-099 |
| 0011 | 22 | GA | | | 66-0 | 26-13-11 | D41354J | | 28 | | D41936P | | 3 | | 115-199 |
| 0012 | 20 | GA | | | 67-0 | 26-13-11 | D41354J | | 34 | | D41936P | | 7 | | 001-099 |
| 0012 | 22 | GA | | | 66-0 | 26-13-11 | D41354J | | 34 | | D41936P | | 7 | | 115-199 |
| 0013 | 20 | GA | | | 56-0 | 74-31-11 | D41354J | | 3 | | SM00001 | | | 9 | 001-099 |
| 0013 | 20 | GA | | | 63-0 | 74-31-11 | D41354J | | 3 | | D41938P | | 1 | | 115-199 |
| 0014 | 20 | GA | | | 65-0 | 74-31-11 | D41354J | | 2 | | D41938P | | 2 | | 001-099 |
| 0014 | 20 | GA | | | 63-0 | 74-31-11 | D41354J | | 2 | | D41938P | | 2 | | 115-199 |
| 0015 | 22 | GA | | | 65-0 | 78-34-11 | D41354J | | 32 | | D41938P | | 3 | | 001-099 |
| 0015 | 22 | GA | | | 63-0 | 78-34-11 | D41354J | | 32 | | D41938P | | 3 | | 115-199 |
| 0016 | 20 | GA | | | 65-0 | 80-11-11 | D41354J | | 12 | | D41938P | | 4 | | 001-099 |
| 0016 | 20 | GA | | | 63-0 | 80-11-11 | D41354J | | 12 | | D41938P | | 4 | | 115-199 |
| 0017 | 20 | GA | | | 65-0 | 80-11-11 | D41354J | | 13 | | D41938P | | 5 | | 001-099 |
| 0017 | 20 | GA | | | 63-0 | 80-11-11 | D41354J | | 13 | | D41938P | | 5 | | 115-199 |
| 0018 | 20 | GA | | | 65-0 | 80-11-11 | D41354J | | 14 | | D41938P | | 6 | | 001-099 |
| 0018 | 20 | GA | | | 63-0 | 80-11-11 | D41354J | | 14 | | D41938P | | 6 | | 115-199 |
| 0020 | 24 | GK | | | 16-0 | 80-11-11 | D41764P | | 18 | | D41938P | | 8 | | 001-099 |
| 0020 | 24 | GK | | | 20-0 | 80-11-11 | D41764P | | 18 | | D41938P | | 8 | | 115-199 |
| 0021 | 24 | GK | | | 16-0 | 80-11-11 | D41764P | | 19 | | D41938P | | 9 | | 001-099 |
| 0021 | 24 | GK | | | 20-0 | 80-11-11 | D41764P | | 19 | | D41938P | | 9 | | 115-199 |
| 0022 | 22 | GA | | | 67-0 | SPARE | D41936P | | 8 | | D41354J | | 30 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4230 | 286N4230 | | | | E/E SHELF DISC TO LEFT WING BODY DISC- (continued) | | | | | | | | | | | |
| 0022 | 22 | | GA | | 66-0 | SPARE | | D41936P | | 8 | | D41354J | | 30 | | 115-199 |
| 0023 | 20 | | GA | | 67-0 | SPARE | | D41936P | | 9 | | D41354J | | 31 | | 001-099 |
| 0023 | 20 | | GA | | 66-0 | SPARE | | D41936P | | 9 | | D41354J | | 31 | | 115-199 |
| 0024 | 22 | | GA | | 23-0 | SPARE | | D41936P | | 2 | | D41764P | | 20 | | ALL |
| 0026 | 20 | | GA | | 68-0 | SPARE | | D41354J | | 19 | | D41764P | | 17 | | 001-099 |
| 0026 | 20 | | GA | | 67-0 | SPARE | | D41354J | | 19 | | D41764P | | 17 | | 115-199 |
| 0027 | 22 | | GA | | 68-0 | SPARE | | D41354J | | 17 | | D41764P | | 12 | | 001-099 |
| 0027 | 22 | | GA | | 67-0 | SPARE | | D41354J | | 17 | | D41764P | | 12 | | 115-199 |
| 0028 | 22 | | GA | | 68-0 | SPARE | | D41354J | | 16 | | D41764P | | 11 | | 001-099 |
| 0028 | 22 | | GA | | 67-0 | SPARE | | D41354J | | 16 | | D41764P | | 11 | | 115-199 |
| 0029 | 22 | | GA | | 68-0 | SPARE | | D41354J | | 18 | | D41764P | | 13 | | 001-099 |
| 0029 | 22 | | GA | | 67-0 | SPARE | | D41354J | | 18 | | D41764P | | 13 | | 115-199 |
| 0030 | 20 | | GA | | 42-0 | 74-31-11 | | D03580 | | 2 | | D41938P | | 13 | | ALL |
| 0031 | 20 | | GA | | 42-0 | 74-31-11 | | D03580 | | 3 | | D41938P | | 10 | | ALL |
| 0032 | 20 | | GA | | 42-0 | 74-31-11 | | D03580 | | 1 | | D41938P | | 7 | | ALL |
| 0035 | 24 | | GK | | 16-0 | SPARE | | D41764P | | 15 | | D41938P | | 12 | | 001-099 |
| 0035 | 24 | | GK | | 20-0 | 74-31-11 | | D41764P | | 26 | | D41938P | | 12 | | 115-199 |
| 0036 | 22 | | GA | | 23-0 | 26-11-11 | | D41764P | | 21 | | D41936P | | 12 | | 001-099 |
| 0036 | 22 | | GA | | 23-0 | 26-11-11 | | D41764P | | 28 | | D41936P | | 12 | | 115-199 |
| 0041 | 20 | | GA | | 42-0 | 74-31-11 | | D03580 | | 5 | | D41938P | | 21 | | 001-099 |
| 0041 | 20 | | GA | | 41-0 | 74-31-11 | | D03580 | | 5 | | D41938P | | 21 | | 115-199 |
| 0042 | 20 | | GA | | 46-0 | 74-31-11 | | D03580 | | 4 | | SM00001 | | | 9 | 001-099 |
| 0043 | 20 | | GA | | 10-0 | 74-31-11 | | D41938P | | 22 | | SM00001 | | | 9 | 001-099 |
| 1002 | 20 | | GE | T | 65-0 | 74-31-11 | | D41354J | | 15 | | D41938P | | 20 | | ALL |
| 1002Z | | | | T | 0-0 | 74-31-11 | | D41354J | | S/R | | GD03618 | | ST.. | E | ALL |
| 2501B | 22 | | GU | AA | 68-0 | 77-12-11 | | D41354J | | 5 | | D41764P | | 4 | | 001-099 |
| 2501B | 22 | | GU | AA | 67-0 | 77-12-11 | | D41354J | | 5 | | D41764P | | 4 | | 115-199 |
| 2501R | 22 | | GU | AA | 0-0 | 77-12-11 | | D41354J | | 4 | | D41764P | | 3 | | ALL |
| 2501Z | | | | AA | 0-0 | 77-12-11 | | D41354J | | S/R | | D41764P | | 5 | | ALL |
| 2502B | 22 | | GU | AB | 68-0 | 77-12-21 | | D41354J | | 8 | | D41764P | | 7 | | 001-099 |
| 2502B | 22 | | GU | AB | 67-0 | 77-12-21 | | D41354J | | 8 | | D41764P | | 7 | | 115-199 |
| 2502R | 22 | | GU | AB | 0-0 | 77-12-21 | | D41354J | | 7 | | D41764P | | 6 | | ALL |
| 2502Z | | | | AB | 0-0 | 77-12-21 | | D41354J | | S/R | | D41764P | | 8 | | ALL |
| 2504B | 18 | | GF | AE | 65-0 | 30-34-21 | | D41354J | | 37 | 18 | D41938P | | 17 | 18 | 001-099 |
| 2504B | 18 | | GF | AF | 63-0 | 30-34-21 | | D41354J | | 37 | 18 | D41938P | | 17 | 18 | 115-199 |
| 2504R | 18 | | GF | AE | 0-0 | 30-34-21 | | D41354J | | 38 | 18 | D41938P | | 18 | 18 | 001-099 |
| 2504R | 18 | | GF | AF | 0-0 | 30-34-21 | | D41354J | | 38 | 18 | D41938P | | 18 | 18 | 115-199 |
| 2504Z | | | | AE | 0-0 | 30-34-21 | | D41354J | | S/R | | D41938P | | 19 | 18 | 001-099 |
| 2504Z | | | | AF | 0-0 | 30-34-21 | | D41354J | | S/R | | D41938P | | 19 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4230 | 286N4230 | | | E/E SHELF DISC TO LEFT WING BODY DISC- (continued) | | | | | | | | | | | |
| 4501G | 20 | DU | | AD | 68-0 | 77-21-11 | D41354J | 22 | 4H | | D41764P | 24 | 4H | | 001-099 |
| 4501G | 20 | DU | | AD | 67-0 | 77-21-11 | D41354J | 22 | 4H | | D41764P | 24 | 4H | | 115-199 |
| 4501W | 20 | DU | | AD | 0-0 | 77-21-11 | D41354J | 23 | 4L | | D41764P | 23 | 4L | | ALL |
| 4501Z | | | | AD | 0-0 | 77-21-11 | D41354J | S/R | | | D41764P | 22 | | | 001-099 |
| 4501Z | | | | AD | 0-0 | 77-21-11 | D41354J | S/R | | | D41764P | 25 | | | 115-199 |
| YAAA | | | | | 0-0 | 80-11-11 | GD03045 | ST.. | E | | D41354J | S/R | | | ALL |
| W4232 | 286N4232 | | | E/E SHELF DISC TO LEFT WING BODY DISC- CAT S2C | | | | | | | | | | | |
| 0001 | 18 | GA | | | 87-0 | 73-21-11 | D40018J | 2 | | | TB0116F | A008 | 2 | | 001-099 |
| 0001 | 18 | GA | | | 84-0 | 73-21-11 | D40018J | 2 | | | TB0158F | A011 | 2 | | 115-199 |
| 0004 | 18 | GA | | | 87-0 | 73-21-11 | D40018J | 34 | | | TB0116F | A007 | 2 | | 001-099 |
| 0004 | 18 | GA | | | 84-0 | 73-21-11 | D40018J | 34 | | | TB0100F | A013 | 2 | | 115-199 |
| 0006 | 22 | GA | | | 67-0 | 75-31-11 | D40018J | 1 | | | D41772P | 2 | | | ALL |
| 0007 | 22 | GA | | | 67-0 | 75-31-11 | D40018J | 13 | | | D41772P | 3 | | | ALL |
| 0008 | 16 | GA | | | 63-0 | 75-31-11 | D40018J | 31 | | | D41988P | 1 | | | 001-099 |
| 0008 | 16 | GA | | | 77-0 | 75-31-11 | D40018J | 31 | | | D41988P | 1 | | | 115-199 |
| 0009 | 18 | GA | | | 63-0 | 75-31-11 | D40018J | 33 | | | D41988P | 2 | | | 001-099 |
| 0009 | 18 | GA | | | 77-0 | 75-31-11 | D40018J | 33 | | | D41988P | 2 | | | 115-199 |
| 0010Y | 20 | QB | | | 42-0 | 27-41-21 | D42020P | 1 | | | D40782P | 8 | | | 115-199 |
| 0011Y | 20 | QB | | | 42-0 | 27-41-21 | D42020P | 2 | | | D40782P | 9 | | | 115-199 |
| 0015 | 20 | GA | | | 67-0 | SPARE | D40018J | 15 | | | D41772P | 12 | | | 001-099 |
| 0016 | 20 | GA | | | 67-0 | SPARE | D40018J | 18 | | | D41772P | 18 | | | 001-099 |
| 0018 | 18 | GA | | | 87-0 | 73-21-12 | D40018J | 8 | | | TB0116F | C007 | 2 | | 001-099 |
| 0018 | 18 | GA | | | 84-0 | 73-21-12 | D40018J | 8 | | | TB0100F | C013 | 2 | | 115-199 |
| 0019 | 18 | GA | | | 67-0 | 73-21-12 | D40018J | 7 | | | D41772P | 7 | 18 | | 001-099 |
| 0019 | 18 | GA | | | 67-0 | 73-21-12 | D40018J | 7 | | | D41772P | 23 | 18 | | 115-199 |
| 0022 | 24 | GK | | | 0-7 | 77-31-11 | D41772P | 17 | | | D41772P | 25 | | | 001-099 |
| 0022 | 24 | GK | | | 1-0 | 77-31-11 | D41772P | 17 | | | D41772P | 25 | | | 115-199 |
| 0023 | 22 | GA | | | 2-0 | 77-31-11 | D40018J | 22 | | | D40018J | 39 | | | ALL |
| 0024 | 22 | GA | | | 2-0 | 77-31-11 | D40018J | 11 | | | D40018J | 26 | | | ALL |
| 0025 | 22 | GA | | | 2-0 | 77-31-11 | D40018J | 10 | | | D40018J | 9 | | | ALL |
| 1002 | 20 | GE | T | | 66-0 | 77-11-11 | D40018J | 3 | | | D41782P | 7 | | | 001-099 |
| 1002 | 20 | GE | T | | 67-0 | 77-11-11 | D40018J | 3 | | | D41782P | 7 | | | 115-199 |
| 1002Z | | | | T | 0-0 | 77-11-11 | D40018J | S/R | | | GD03616 | ST.. | E | | ALL |
| 2001B | 20 | GB | AA | | 66-0 | 22-33-11 | D40018J | 14 | | | D41782P | 2 | | | 001-099 |
| 2001B | 20 | GB | AA | | 67-0 | 22-33-11 | D40018J | 14 | | | D41782P | 2 | | | 115-199 |
| 2001R | 20 | GB | AA | | 0-0 | 22-33-11 | D40018J | 16 | | | D41782P | 1 | | | ALL |
| 2002B | 20 | GB | AB | | 66-0 | 22-33-11 | D40018J | 35 | | | D41782P | 3 | | | 001-099 |
| 2002B | 20 | GB | AB | | 67-0 | 22-33-11 | D40018J | 35 | | | D41782P | 3 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4232 | 286N4232 | | | E/E SHELF DISC TO LEFT WING BODY DISC- CAT S2C (continued) | | | | | | | | | | | |
| 2002R | 20 | GB | AB | | 0-0 | 22-33-11 | D40018J | 6 | | | D41782P | 4 | | | ALL |
| 2003B | 22 | GB | AH | | 41-0 | 27-51-41 | D40782P | 12 | | | D42228P | 2 | | | 115-199 |
| 2003R | 22 | GB | AH | | 0-0 | 27-51-41 | D40782P | 5 | | | D42228P | 1 | | | 115-199 |
| 2501B | 22 | GU | AD | | 67-0 | 77-12-31 | D40018J | 30 | | | D41772P | 9 | | | ALL |
| 2501R | 22 | GU | AD | | 0-0 | 77-12-31 | D40018J | 29 | | | D41772P | 8 | | | ALL |
| 2501Z | | | AD | | 0-0 | 77-12-31 | D40018J | S/R | | | D41772P | 10 | | | ALL |
| 2503B | 20 | GU | AL | | 66-0 | SPARE | D40018J | 17 | | | D41782P | 8 | | | 001-099 |
| 2503R | 20 | GU | AL | | 0-0 | SPARE | D40018J | 19 | | | D41782P | 9 | | | 001-099 |
| 2503Z | | | AL | | 0-0 | SPARE | D40018J | S/R | | | D41782P | 10 | | | 001-099 |
| 2504B | 20 | GU | AM | | 63-0 | SPARE | D40018J | 20 | | | D41988P | 3 | | | 001-099 |
| 2504R | 20 | GU | AM | | 0-0 | SPARE | D40018J | 21 | | | D41988P | 4 | | | 001-099 |
| 2504Z | | | AM | | 0-0 | SPARE | D40018J | S/R | | | D41988P | 5 | | | 001-099 |
| 4001B | 22 | GD | AJ | | 41-0 | 27-51-41 | D40782P | 7 | | | D42228P | 4 | | | 115-199 |
| 4001G | 22 | GD | AJ | | 0-0 | 27-51-41 | D40782P | 11 | | | D42228P | 6 | | | 115-199 |
| 4001R | 22 | GD | AJ | | 0-0 | 27-51-41 | D40782P | 6 | | | D42228P | 3 | | | 115-199 |
| 4001Y | 22 | GD | AJ | | 0-0 | 27-51-41 | D40782P | 10 | | | D42228P | 5 | | | 115-199 |
| 4501R | 20 | RJ | AE | | 67-0 | 77-31-11 | D40018J | 40 | | | D41772P | 27 | | | ALL |
| 4501W | 20 | RJ | AE | | 0-0 | 77-31-11 | D40018J | 25 | | | D41772P | 26 | | | ALL |
| 4501Z | | | AE | | 0-0 | 77-31-11 | D40018J | 23 | | | D41772P | 14 | | | ALL |
| 4502R | 20 | RJ | AF | | 67-0 | 77-31-11 | D40018J | 42 | | | D41772P | 29 | | | ALL |
| 4502W | 20 | RJ | AF | | 0-0 | 77-31-11 | D40018J | 41 | | | D41772P | 28 | | | ALL |
| 4502Z | | | AF | | 0-0 | 77-31-11 | D40018J | 24 | | | D41772P | 16 | | | ALL |
| 5001B | 22 | GU | AC | | 67-0 | 77-11-11 | D40018J | 4 | | | D41772P | 4 | | | ALL |
| 5001R | 22 | GU | AC | | 0-0 | 77-11-11 | D40018J | 5 | | | D41772P | 5 | | | ALL |
| 5001Z | | | AC | | 0-0 | 77-11-11 | D40018J | S/R | | | D41772P | 6 | | | ALL |
| 5002B | 22 | GU | AG | | 67-0 | 77-11-11 | D40018J | 36 | | | D41772P | 20 | | | ALL |
| 5002R | 22 | GU | AG | | 0-0 | 77-11-11 | D40018J | 37 | | | D41772P | 21 | | | ALL |
| 5002Z | | | AG | | 0-0 | 77-11-11 | D40018J | S/R | | | D41772P | 22 | | | ALL |
| YAAA | | | | | 0-0 | 77-11-11 | GD02407 | ST.. | E | | D40018J | S/R | | | ALL |
| W4234 | 286N4234 | | | E/E SHELF DISC TO RIGHT WING BODY DISC | | | | | | | | | | | |
| 0001 | 22 | GA | | | 43-0 | 73-33-11 | D41358J | 1 | | | D41774P | 1 | | | ALL |
| 0002 | 22 | GA | | | 43-0 | 73-34-11 | D41358J | 21 | | | D41774P | 2 | | | ALL |
| 0003 | 22 | GA | | | 43-0 | 79-33-11 | D41358J | 10 | | | D41774P | 3 | | | ALL |
| 0004 | 22 | GA | | | 43-0 | 79-35-11 | D41358J | 11 | | | D41774P | 10 | | | ALL |
| 0005R | 20 | QA | | | 51-0 | 26-11-21 | D41358J | 33 | | | D41940P | 1 | | | ALL |
| 0006R | 20 | QA | | | 51-0 | 26-11-21 | D41358J | 25 | | | D41940P | 13 | | | ALL |
| 0007R | 20 | QA | | | 51-0 | 26-11-21 | D41358J | 27 | | | D41940P | 15 | | | ALL |
| 0008 | 20 | GA | | | 51-0 | 26-13-21 | D41358J | 28 | | | D41940P | 3 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4234 | 286N4234 | | | E/E SHELF DISC TO RIGHT WING BODY DISC (continued) | | | | | | | | | | | |
| 0009 | 20 | | GA | | 51-0 | 26-13-21 | D41358J | | 34 | | D41940P | | 5 | | ALL |
| 0010 | 22 | | GA | | 26-0 | 26-11-21 | D42008P | | 9 | | D41940P | | 6 | | 001-099 |
| 0010 | 20 | | GA | | 25-0 | 26-11-21 | D42008P | | 9 | | D41940P | | 6 | | 115-199 |
| 0011 | 22 | | GA | | 43-0 | SPARE | D41358J | | 19 | | D41774P | | 14 | | ALL |
| 0012 | 22 | | GA | | 51-0 | SPARE | D41358J | | 20 | | D41940P | | 7 | | ALL |
| 0013 | 22 | | GA | | 23-0 | 26-13-21 | D41774P | | 15 | | D41940P | | 8 | | 001-099 |
| 0013 | 22 | | GA | | 22-0 | 26-13-21 | D41774P | | 15 | | D41940P | | 8 | | 115-199 |
| 0014 | 22 | | GA | | 23-0 | SPARE | D41774P | | 16 | | D41940P | | 9 | | ALL |
| 0015 | 20 | | GA | | 72-0 | 74-31-21 | D41358J | | 3 | | SM00001 | | 9 | | 001-099 |
| 0015 | 20 | | GA | | 48-0 | 74-31-21 | D41358J | | 3 | | D42008P | | 1 | | 115-199 |
| 0016 | 20 | | GA | | 49-0 | 74-31-21 | D41358J | | 2 | | D42008P | | 2 | | 001-099 |
| 0016 | 20 | | GA | | 48-0 | 74-31-21 | D41358J | | 2 | | D42008P | | 2 | | 115-199 |
| 0017 | 22 | | GA | | 49-0 | 78-34-21 | D41358J | | 32 | | D42008P | | 3 | | 001-099 |
| 0017 | 22 | | GA | | 48-0 | 78-34-21 | D41358J | | 32 | | D42008P | | 3 | | 115-199 |
| 0018 | 20 | | GA | | 49-0 | 80-11-21 | D41358J | | 12 | | D42008P | | 4 | | 001-099 |
| 0018 | 20 | | GA | | 48-0 | 80-11-21 | D41358J | | 12 | | D42008P | | 4 | | 115-199 |
| 0019 | 20 | | GA | | 49-0 | 80-11-21 | D41358J | | 13 | | D42008P | | 5 | | 001-099 |
| 0019 | 20 | | GA | | 48-0 | 80-11-21 | D41358J | | 13 | | D42008P | | 5 | | 115-199 |
| 0020 | 20 | | GA | | 49-0 | 80-11-21 | D41358J | | 14 | | D42008P | | 6 | | 001-099 |
| 0020 | 20 | | GA | | 48-0 | 80-11-21 | D41358J | | 14 | | D42008P | | 6 | | 115-199 |
| 0021 | 24 | | GK | | 22-0 | 80-11-21 | D41774P | | 17 | | D42008P | | 7 | | 001-099 |
| 0021 | 24 | | GK | | 19-0 | 80-11-21 | D41774P | | 17 | | D42008P | | 7 | | 115-199 |
| 0022 | 24 | | GK | | 22-0 | 80-11-21 | D41774P | | 18 | | D42008P | | 8 | | 001-099 |
| 0022 | 24 | | GK | | 19-0 | 80-11-21 | D41774P | | 18 | | D42008P | | 8 | | 115-199 |
| 0024 | 24 | | GK | | 22-0 | SPARE | D41774P | | 20 | | D42008P | | 10 | | 001-099 |
| 0024 | 24 | | GK | | 19-0 | SPARE | D41774P | | 20 | | D42008P | | 10 | | 115-199 |
| 0025 | 22 | | GA | | 51-0 | SPARE | D41358J | | 30 | | D41940P | | 10 | | ALL |
| 0026 | 22 | | GA | | 51-0 | SPARE | D41358J | | 31 | | D41940P | | 11 | | ALL |
| 0027 | 20 | | GA | | 48-0 | 74-31-21 | D03582 | | 2 | | D42008P | | 13 | | 001-099 |
| 0027 | 20 | | GA | | 46-0 | 74-31-21 | D03582 | | 2 | | D42008P | | 13 | | 115-199 |
| 0028 | 20 | | GA | | 48-0 | 74-31-21 | D03582 | | 3 | | D42008P | | 11 | | 001-099 |
| 0028 | 20 | | GA | | 46-0 | 74-31-21 | D03582 | | 3 | | D42008P | | 11 | | 115-199 |
| 0029 | 20 | | GA | | 48-0 | 74-31-21 | D03582 | | 1 | | D42008P | | 12 | | 001-099 |
| 0029 | 20 | | GA | | 46-0 | 74-31-21 | D03582 | | 1 | | D42008P | | 12 | | 115-199 |
| 0032 | 24 | | GK | | 22-0 | SPARE | D41774P | | 21 | | D42008P | | 14 | | 001-099 |
| 0032 | 24 | | GK | | 19-0 | 74-31-21 | D41774P | | 21 | | D42008P | | 14 | | 115-199 |
| 0033 | 20 | | GA | | 22-0 | SPARE | D41774P | | 24 | | D42008P | | 15 | | 001-099 |
| 0033 | 20 | | GA | | 19-0 | 29-35-11 | D41774P | | 24 | | D42008P | | 15 | | 115-199 |
| 0041 | 20 | | GA | | 48-0 | 74-31-21 | D03582 | | 5 | | D42008P | | 16 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|----|-------------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4234 | 286N4234 | | | | E/E SHELF DISC TO RIGHT WING BODY DISC (continued) | | | | | | | | | | | | |
| 0041 | 20 | | GA | | 46-0 | 74-31-21 | | D03582 | | 5 | | D42008P | | 16 | | 115-199 | |
| 0042 | 20 | | GA | | 1-0 | 74-31-21 | | D03582 | | 4 | | SM00001 | | 9 | | 001-099 | |
| 0043 | 20 | | GA | | 48-0 | 74-31-21 | | D42008P | | 21 | | SM00001 | | 9 | | 001-099 | |
| 1002 | 20 | | GE | T | 49-0 | 74-31-21 | | D41358J | | 15 | | D42008P | | 20 | | 001-099 | |
| 1002 | 20 | | GE | T | 48-0 | 74-31-21 | | D41358J | | 15 | | D42008P | | 20 | | 115-199 | |
| 1002Z | | | | T | 0-0 | 74-31-21 | | D41358J | | S/R | | GD03622 | ST.. | E | | 001-099 | |
| 1002Z | | | | T | 0-0 | 74-31-21 | | D41358J | | S/R | | GD03624 | ST.. | E | | 115-199 | |
| 2501B | 22 | | GU | AA | 43-0 | 77-12-11 | | D41358J | | 5 | | D41774P | | 5 | | ALL | |
| 2501R | 22 | | GU | AA | 0-0 | 77-12-11 | | D41358J | | 4 | | D41774P | | 4 | | ALL | |
| 2501Z | | | | AA | 0-0 | 77-12-11 | | D41358J | | S/R | | D41774P | | 6 | | ALL | |
| 2502B | 22 | | GU | AB | 43-0 | 77-12-21 | | D41358J | | 8 | | D41774P | | 8 | | ALL | |
| 2502R | 22 | | GU | AB | 0-0 | 77-12-21 | | D41358J | | 7 | | D41774P | | 7 | | ALL | |
| 2502Z | | | | AB | 0-0 | 77-12-21 | | D41358J | | S/R | | D41774P | | 9 | | ALL | |
| 2503B | 22 | | GU | AC | 43-0 | SPARE | | D41358J | | 17 | | D41774P | | 12 | | ALL | |
| 2503R | 22 | | GU | AC | 0-0 | SPARE | | D41358J | | 16 | | D41774P | | 11 | | ALL | |
| 2503Z | | | | AC | 0-0 | SPARE | | D41358J | | 18 | | D41774P | | 13 | | ALL | |
| 2504B | 18 | | GF | AE | 49-0 | 30-34-22 | | D41358J | | 37 | 18 | D42008P | | 17 | 18 | 001-099 | |
| 2504B | 18 | | GF | AE | 48-0 | 30-34-22 | | D41358J | | 37 | 18 | D42008P | | 17 | 18 | 115-199 | |
| 2504R | 18 | | GF | AE | 0-0 | 30-34-22 | | D41358J | | 38 | 18 | D42008P | | 18 | 18 | ALL | |
| 2504Z | | | | AE | 0-0 | 30-34-22 | | D41358J | | S/R | | D42008P | | 19 | 18 | ALL | |
| 4501G | 20 | | DU | AD | 43-0 | 77-21-11 | | D41358J | | 22 | | D41774P | | 22 | | ALL | |
| 4501W | 20 | | DU | AD | 0-0 | 77-21-11 | | D41358J | | 23 | | D41774P | | 19 | | 001-099 | |
| 4501W | 20 | | DU | AD | 0-0 | 77-21-11 | | D41358J | | 23 | | D41774P | | 31 | | 115-199 | |
| 4501Z | | | | AD | 0-0 | 77-21-11 | | D41358J | | S/R | | D41774P | | 23 | | ALL | |
| YAAA | | | | | 0-0 | 80-11-21 | | GD03063 | | ST.. | E | D41358J | | S/R | | ALL | |
| W4236 | 286N4236 | | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC | | | | | | | | | | | | |
| 0001 | 22 | | GA | | 48-0 | 76-11-12 | | D40004J | | 28 | | D42010P | | 1 | | ALL | |
| 0002 | 22 | | GA | | 48-0 | 76-11-12 | | D40004J | | 29 | | D42010P | | 2 | | ALL | |
| 0003 | 22 | | GA | | 69-0 | 76-11-12 | | D40899P | | 15 | | D40004J | | 26 | | 001-099 | |
| 0003 | 22 | | GA | | 69-0 | 76-11-12 | | D40004J | | 26 | | D40899P | | 15 | | 115-199 | |
| 0005 | 18 | | GA | | 48-0 | 73-21-21 | | D04064 | | 2 | | TB0114F | C006 | 2 | | 001-099 | |
| 0005 | 18 | | GA | | 47-0 | 73-21-21 | | D04064 | | 2 | | TB0159F | C006 | 2 | | 115-199 | |
| 0006 | 24 | | GK | | 28-0 | 73-21-21 | | D04064 | | 1 | | D42010P | | 22 | | 001-099 | |
| 0006 | 24 | | GK | | 31-0 | 73-21-21 | | D04064 | | 1 | | D42010P | | 22 | | 115-199 | |
| 0009 | 22 | | GA | | 20-0 | 76-11-12 | | D40899P | | 14 | | D01588 | | 7 | | 001-099 | |
| 0009 | 22 | | GA | | 25-0 | 76-11-12 | | D40899P | | 14 | | D01588 | | 7 | | 115-199 | |
| 0010 | 22 | | GA | | 5-0 | 76-11-12 | | D01588 | | 19 | | TB0058X | B001 | BJ | | 001-099 | |
| 0010 | 22 | | GA | | 11-0 | 76-11-12 | | D01588 | | 19 | | TB0058X | B001 | BJ | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|----------|---|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | | 286N4236 | | | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | |
| 0012 | 22 | GA | | | 43-0 | 28-42-11 | D40004J | 30 | | | D41776P | 1 | | | 001-099 |
| 0012 | 22 | GA | | | 42-0 | 28-42-11 | D40004J | 30 | | | D41776P | 1 | | | 115-199 |
| 0013R | 20 | QA | | | 51-0 | 26-11-21 | D41946P | 13 | | | D40016J | 4 | | | 001-099 |
| 0013R | 20 | QA | | | 50-0 | 26-11-21 | D40016J | 4 | | | D41946P | 13 | | | 115-199 |
| 0014R | 20 | QA | | | 51-0 | 26-11-21 | D41946P | 1 | | | D40016J | 20 | | | 001-099 |
| 0014R | 20 | QA | | | 50-0 | 26-11-21 | D40016J | 20 | | | D41946P | 1 | | | 115-199 |
| 0015R | 20 | QA | | | 51-0 | 26-11-21 | D41946P | 30 | | | D40016J | 6 | | | 001-099 |
| 0015R | 20 | QA | | | 50-0 | 26-11-21 | D40016J | 6 | | | D41946P | 30 | | | 115-199 |
| 0016 | 22 | GA | | | 28-0 | 26-11-21 | TB0159A | C005 | 2 | | D41946P | 4 | | | 001-099 |
| 0016 | 22 | GA | | | 27-0 | 26-11-21 | TB0159A | C005 | 2 | | D41946P | 4 | | | 115-199 |
| 0017 | 22 | GA | | | 5-0 | 26-11-21 | D01588 | 2 | | | TB0159A | A004 | 2 | | 001-099 |
| 0017 | 22 | GA | | | 10-0 | 26-11-21 | D01588 | 2 | | | TB0159A | A004 | 2 | | 115-199 |
| 0018 | 22 | GA | | | 5-0 | 26-11-21 | D01588 | 25 | | | TB0159A | A003 | 2 | | 001-099 |
| 0018 | 22 | GA | | | 10-0 | 26-11-21 | D01588 | 25 | | | TB0159A | A003 | 2 | | 115-199 |
| 0019 | 22 | GA | | | 28-0 | 26-11-21 | D01588 | 10 | | | D41946P | 5 | | | 001-099 |
| 0019 | 22 | GA | | | 32-0 | 26-11-21 | D01588 | 10 | | | D41946P | 5 | | | 115-199 |
| 0020 | 22 | GA | | | 28-0 | 26-11-21 | TB0159A | C003 | 2 | | D41946P | 6 | | | 001-099 |
| 0020 | 22 | GA | | | 27-0 | 26-11-21 | TB0159A | C003 | 2 | | D41946P | 6 | | | 115-199 |
| 0021 | 22 | GA | | | 23-0 | 26-11-21 | D41776P | 2 | | | D41946P | 7 | | | ALL |
| 0022 | 22 | GA | | | 29-0 | 26-11-21 | D03492 | 8 | | | D41946P | 8 | | | 001-099 |
| 0022 | 22 | GA | | | 28-0 | 26-11-21 | D03492 | 8 | | | D41946P | 8 | | | 115-199 |
| 0023 | 22 | GA | | | 6-0 | 26-11-21 | D03492 | 9 | | | GD01650 | DC.. | 2 | | 001-099 |
| 0023 | 20 | GA | | | 5-0 | 26-11-21 | D03492 | 9 | | | GD01650 | DC.. | 2 | *1 | 115-199 |
| 0024 | 20 | GA | | | 5-0 | 31-51-33 | D01588 | 15 | | | GD00742 | DC.. | 2 | | 001-099 |
| 0024 | 20 | GA | | | 10-0 | 31-51-33 | D01588 | 15 | | | GD00742 | DC.. | 2 | | 115-199 |
| 0025 | 22 | GA | | | 45-0 | 31-51-33 | D01588 | 4 | | | D42014P | 1 | | | 001-099 |
| 0025 | 22 | GA | | | 50-0 | 31-51-33 | D01588 | 4 | | | D42014P | 1 | | | 115-199 |
| 0026 | 20 | GA | | | 51-0 | 26-13-21 | D41946P | 41 | | | D40016J | 8 | | | 001-099 |
| 0026 | 20 | GA | | | 50-0 | 26-13-21 | D41946P | 41 | | | D40016J | 8 | | | 115-199 |
| 0027 | 20 | GA | | | 51-0 | 26-13-21 | D41946P | 10 | | | D40016J | 12 | | | 001-099 |
| 0027 | 20 | GA | | | 50-0 | 26-13-21 | D41946P | 10 | | | D40016J | 12 | | | 115-199 |
| 0028 | 22 | GA | | | 23-0 | 26-13-21 | D41946P | 52 | | | D41776P | 3 | | | ALL |
| 0029 | 22 | GA | | | 53-0 | 26-18-21 | D41990P | 1 | | | D40016J | 2 | | | 001-099 |
| 0029 | 20 | GA | | | 51-0 | 26-18-21 | D41990P | 1 | | | D40016J | 2 | | | 115-199 |
| 0030 | 22 | GA | | | 53-0 | 26-18-21 | D41990P | 2 | | | D40016J | 3 | | | 001-099 |
| 0030 | 20 | GA | | | 51-0 | 26-18-21 | D41990P | 2 | | | D40016J | 3 | | | 115-199 |
| 0031 | 22 | GA | | | 73-0 | 26-18-11 | D41990P | 3 | | | D40364J | 2 | | | 001-099 |
| 0031 | 20 | GA | | | 73-0 | 26-18-11 | D41990P | 3 | | | D40364J | 2 | | | 115-199 |
| 0032 | 22 | GA | | | 73-0 | 26-18-11 | D41990P | 4 | | | D40364J | 3 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | 286N4236 | | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0032 | 20 | | GA | | 73-0 | 26-18-11 | | D41990P | | | | D40364J | | | | 115-199 |
| 0033 | 22 | | GA | | 73-0 | 26-18-11 | | D41990P | | | | D40364J | | | | 001-099 |
| 0033 | 20 | | GA | | 73-0 | 26-18-11 | | D41990P | | | | D40364J | | | | 115-199 |
| 0034 | 22 | | GA | | 73-0 | 26-18-11 | | D41990P | | | | D40364J | | | | 001-099 |
| 0034 | 20 | | GA | | 73-0 | 26-18-11 | | D41990P | | | | D40364J | | | | 115-199 |
| 0035 | 20 | | GA | | 5-0 | 28-22-21 | | D01588 | | | | TB0058X | C008 | BJ | | 001-099 |
| 0035 | 20 | | GA | | 11-0 | 28-22-21 | | D01588 | | | | TB0058X | C008 | BJ | | 115-199 |
| 0036 | 20 | | GA | | 5-0 | 28-22-21 | | D01588 | | | | TB0158Y | A001 | BJ | | 001-099 |
| 0036 | 20 | | GA | | 10-0 | 28-22-21 | | D01588 | | | | TB0158Y | A001 | BJ | | 115-199 |
| 0037 | 20 | | GA | | 20-0 | 28-22-21 | | D01588 | | | | D40899P | | | | 001-099 |
| 0037 | 20 | | GA | | 25-0 | 28-22-21 | | D01588 | | | | D40899P | | | | 115-199 |
| 0038Y | 20 | | QB | | 5-0 | 27-41-21 | | D40899P | | | | TB0100X | B004 | BJ | | 001-099 |
| 0038Y | 20 | | QB | | 4-0 | 27-41-21 | | D40899P | | | | TB0100X | B004 | BJ | | 115-199 |
| 0039 | 20 | | GA | | 27-0 | 28-22-21 | | D40899P | | | | D41946P | | | | ALL |
| 0040 | 20 | | GA | | 28-0 | 28-22-21 | | TB0158Y | A001 | BJ | | D41946P | | | | 001-099 |
| 0040 | 20 | | GA | | 27-0 | 28-22-21 | | TB0158Y | A001 | BJ | | D41946P | | | | 115-199 |
| 0041 | 22 | | GA | | 28-0 | 28-22-21 | | D40899P | | | | D41950P | | | | 001-099 |
| 0041 | 22 | | GA | | 29-0 | 28-22-21 | | D40899P | | | | D41950P | | | | 115-199 |
| 0042 | 22 | | GA | | 14-0 | 28-22-21 | | D41946P | | | | D41950P | | | | 001-099 |
| 0042 | 22 | | GA | | 16-0 | 28-22-21 | | D41946P | | | | D41950P | | | | 115-199 |
| 0043 | 22 | | GA | | 23-0 | 26-11-22 | | D41946P | | | | D41776P | | | | ALL |
| 0044 | 22 | | GA | | 23-0 | 26-11-22 | | D41946P | | | | D41776P | | | | ALL |
| 0045 | 22 | | GA | | 28-0 | 26-11-22 | | D03234 | | | | D41946P | | | | ALL |
| 0046 | 22 | | GA | | 50-0 | 26-11-22 | | D41946P | | | | D40274J | | | | 001-099 |
| 0046 | 20 | | GA | | 50-0 | 26-11-22 | | D41946P | | | | D40274J | | | | 115-199 |
| 0047 | 22 | | GA | | 50-0 | 26-11-22 | | D41946P | | | | D40274J | | | | 001-099 |
| 0047 | 20 | | GA | | 50-0 | 26-11-22 | | D41946P | | | | D40274J | | | | 115-199 |
| 0048 | 22 | | GA | | 50-0 | 26-12-21 | | D41946P | | | | D40274J | | | | 001-099 |
| 0048 | 22 | | GA | | 50-0 | 26-12-21 | | D41946P | | | | D40274J | | | | 115-199 |
| 0049 | 22 | | GA | | 50-0 | 26-12-21 | | D41946P | | | | D40274J | | | | ALL |
| 0050 | 22 | | GA | | 29-0 | 26-12-21 | | D41946P | | | | D03492 | | | | 001-099 |
| 0050 | 22 | | GA | | 28-0 | 26-12-21 | | D41946P | | | | D03492 | | | | 115-199 |
| 0051 | 20 | | GA | | 6-0 | 26-12-21 | | D03492 | | | | GD01650 | DC.. | 2 | | 001-099 |
| 0051 | 20 | | GA | | 5-0 | 26-12-21 | | D03492 | | | | GD01650 | DC.. | 2 | *1 | 115-199 |
| 0052 | 22 | | GA | | 23-0 | 26-12-21 | | D41946P | | | | D41776P | | | | 001-099 |
| 0052 | 22 | | GA | | 23-0 | 26-12-21 | | D41946P | | | | D41776P | | | | 115-199 |
| 0053 | 22 | | GA | | 41-0 | SPARE | | D40899P | CAP | Y | | D42010P | CAP | Y | | 001-002 |
| 0053 | 22 | | GA | | 42-0 | SPARE | | D40899P | CAP | Y | | D42010P | CAP | Y | | 115-199 |
| 0054 | 22 | | GA | | 41-0 | SPARE | | D40899P | CAP | Y | | D42010P | CAP | Y | | 001-002 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | | | | | |
|--------------|-----------------|---|------|-----|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|--|--|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | | | |
| W4236 | 286N4236 | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | | | | | | | |
| 0054 | 22 | | GA | | 42-0 | SPARE | D40899P | CAP | Y | | D42010P | CAP | Y | | 115-199 | | | | |
| 0055 | 22 | | GA | | 27-0 | 78-34-21 | D42010P | | 7 | | D42014P | | 2 | | 001-099 | | | | |
| 0055 | 22 | | GA | | 29-0 | 78-34-21 | D42010P | | 7 | | D42014P | | 2 | | 115-199 | | | | |
| 0056 | 22 | | GA | | 5-0 | 78-34-21 | D01588 | | 20 | | TB0158Y | A002 | BJ | | 001-099 | | | | |
| 0056 | 22 | | GA | | 11-0 | 78-34-21 | D01588 | | 20 | | TB0058Y | A006 | BJ | | 115-199 | | | | |
| 0057 | 22 | | GA | | 43-0 | 78-34-21 | D01588 | | 39 | | D42010P | | 8 | | 001-099 | | | | |
| 0057 | 22 | | GA | | 48-0 | 78-34-21 | D01588 | | 39 | | D42010P | | 8 | | 115-199 | | | | |
| 0058 | 20 | | GA | | 22-0 | 26-21-11 | D01588 | | 9 | | D44104P | | 2 | | 001-099 | | | | |
| 0058 | 20 | | GA | | 28-0 | 26-21-11 | D01588 | | 9 | | D44104P | | 2 | | 115-199 | | | | |
| 0059 | 20 | | GA | | 22-0 | 26-21-11 | D01588 | | 22 | | D44106P | | 2 | | 001-099 | | | | |
| 0059 | 20 | | GA | | 28-0 | 26-21-11 | D01588 | | 22 | | D44106P | | 2 | | 115-199 | | | | |
| 0060 | 20 | | GA | | 5-0 | 26-21-11 | D01588 | | 8 | | SM00007 | | 9 | | 001-099 | | | | |
| 0060 | 20 | | GA | | 12-0 | 26-21-11 | D01588 | | 8 | | SM00007 | | 9 | | 115-199 | | | | |
| 0061 | 20 | | GA | | 5-0 | 26-21-11 | D01588 | | 23 | | SM00006 | | 9 | | 001-099 | | | | |
| 0061 | 20 | | GA | | 12-0 | 26-21-11 | D01588 | | 23 | | SM00006 | | 9 | | 115-199 | | | | |
| 0062 | 22 | | GA | | 41-0 | 26-21-11 | D03234 | | 2 | | D41776P | | 10 | | ALL | | | | |
| 0063 | 22 | | GA | | 29-0 | 26-11-11 | D03492 | | 5 | | D41946P | | 21 | | 001-099 | | | | |
| 0063 | 22 | | GA | | 28-0 | 26-11-11 | D03492 | | 5 | | D41946P | | 21 | | 115-199 | | | | |
| 0064 | 22 | | GA | | 29-0 | 26-11-11 | D03492 | | 7 | | D41946P | | 22 | | 001-099 | | | | |
| 0064 | 22 | | GA | | 28-0 | 26-11-11 | D03492 | | 7 | | D41946P | | 22 | | 115-199 | | | | |
| 0065 | 22 | | GA | | 6-0 | 26-11-11 | D03492 | | 6 | | GD00742 | DC.. | 2 | | 001-099 | | | | |
| 0065 | 20 | | GA | | 5-0 | 26-11-11 | D03492 | | 6 | | GD00742 | DC.. | 2 | | 115-199 | | | | |
| 0066 | 24 | | GK | | 8-0 | 80-11-21 | D42010P | | 9 | | D41990P | | 7 | | ALL | | | | |
| 0067 | 24 | | GK | | 32-0 | 73-21-22 | D04062 | | 34 | | D41990P | | 20 | | 001-099 | | | | |
| 0067 | 20 | | GA | | 8-0 | SPARE | D42010P | | 10 | | D41990P | | 8 | | 115-199 | | | | |
| 0068 | 20 | | GA | | 8-0 | SPARE | D42010P | | 11 | | D41990P | | 9 | | 115-199 | | | | |
| 0069 | 22 | | GA | | 5-0 | 24-22-21 | D01588 | | 21 | | TB0058X | C009 | BJ | | 001-099 | | | | |
| 0069 | 22 | | GA | | 11-0 | 24-22-21 | D01588 | | 21 | | TB0058X | C009 | BJ | | 115-199 | | | | |
| 0070 | 22 | | GA | | 5-0 | 24-22-21 | D01588 | | 40 | | TB0058X | D009 | BJ | | 001-099 | | | | |
| 0070 | 22 | | GA | | 11-0 | 24-22-21 | D01588 | | 40 | | TB0058X | D009 | BJ | | 115-199 | | | | |
| 0071 | 22 | | GA | | 40-0 | 28-22-21 | D40899P | | 23 | | D41776P | | 4 | | ALL | | | | |
| 0072 | 22 | | GA | | 5-0 | 33-16-61 | D40899P | | 8 | | TB0100X | B001 | BJ | | 001-099 | | | | |
| 0072 | 22 | | GA | | 4-0 | 33-16-61 | D40899P | | 8 | | TB0100X | B001 | BJ | | 115-199 | | | | |
| 0073 | 22 | | GA | | 20-0 | 33-16-51 | D03234 | | 4 | | TB0100Y | C009 | BJ | | ALL | | | | |
| 0074 | 22 | | GA | | 20-0 | 33-16-51 | D03234 | | 3 | | TB0100Y | C010 | BJ | | ALL | | | | |
| 0075 | 20 | | GA | | 6-0 | 33-13-52 | D03492 | | 1 | | TB0059Z | | 1 | BJ | 001-099 | | | | |
| 0075 | 20 | | GA | | 5-0 | 33-13-52 | D03492 | | 1 | | TB0059Z | | 1 | BJ | 115-199 | | | | |
| 0076 | 20 | | GA | | 6-0 | 33-13-52 | D03492 | | 2 | | GD01650 | AC.. | 2 | | 001-099 | | | | |
| 0076 | 20 | | GA | | 5-0 | 33-13-52 | D03492 | | 2 | | GD01650 | AC.. | 2 | | 115-199 | | | | |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | 286N4236 | | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0077 | 22 | | GA | | 8-0 | 77-12-42 | | D41990P | | 10 | | D42010P | | 12 | | ALL |
| 0078 | 24 | | GK | | 24-0 | 77-12-42 | | D41990P | | 11 | | D41776P | | 11 | | 001-099 |
| 0078 | 22 | | GA | | 23-0 | 77-12-42 | | D41990P | | 11 | | D41776P | | 11 | | 115-199 |
| 0079 | 24 | | GK | | 5-0 | 21-25-11 | | D03498 | | 11 | | TB0059X | B010 | BJ | | ALL |
| 0080 | 22 | | GA | | 21-0 | 33-16-51 | | D03492 | | 4 | | TB0100Y | C009 | BJ | | 001-099 |
| 0080 | 22 | | GA | | 20-0 | 33-16-51 | | D03492 | | 4 | | TB0100Y | C009 | BJ | | 115-199 |
| 0081 | 22 | | GA | | 21-0 | 33-16-51 | | D03492 | | 3 | | TB0100Y | C010 | BJ | | 001-099 |
| 0081 | 22 | | GA | | 20-0 | 33-16-51 | | D03492 | | 3 | | TB0100Y | C010 | BJ | | 115-199 |
| 0082 | 22 | | GA | | 5-0 | 33-16-61 | | D01588 | | 1 | | TB0058Z | 4 | BJ | | 001-099 |
| 0082 | 22 | | GA | | 11-0 | 33-16-61 | | D01588 | | 1 | | TB0058Z | 4 | BJ | | 115-199 |
| 0083 | 20 | | GA | | 42-0 | SPARE | | D40004J | | 41 | | D41776P | | 12 | | 115-199 |
| 0084 | 20 | | GA | | 48-0 | SPARE | | D40004J | | 25 | | D42010P | | 14 | | 115-199 |
| 0085 | 20 | | GA | | 50-0 | SPARE | | D40016J | | 28 | | D41946P | | 23 | | 115-199 |
| 0086 | 20 | | GA | | 50-0 | SPARE | | D40016J | | 29 | | D41946P | | 24 | | 115-199 |
| 0087 | 22 | | GA | | 5-0 | 33-16-51 | | D40899P | | 9 | | TB0100Y | A009 | BJ | | 001-099 |
| 0087 | 22 | | GA | | 4-0 | 33-16-51 | | D40899P | | 9 | | TB0100Y | A009 | BJ | | 115-199 |
| 0088 | 22 | | GA | | 5-0 | 33-16-51 | | D40899P | | 10 | | TB0100X | D001 | BJ | | 001-099 |
| 0088 | 22 | | GA | | 4-0 | 33-16-51 | | D40899P | | 10 | | TB0100X | D001 | BJ | | 115-199 |
| 0089 | 20 | | GA | | 54-0 | SPARE | | D40274J | | 9 | | D42014P | | 9 | | 001-099 |
| 0089 | 20 | | GA | | 55-0 | SPARE | | D40274J | | 9 | | D42014P | | 7 | | 115-199 |
| 0090 | 22 | | GA | | 70-0 | 29-11-21 | | D40016J | | 10 | | D01588 | | 37 | | 001-099 |
| 0090 | 20 | | GA | | 74-0 | 29-11-21 | | D40016J | | 10 | | D01588 | | 37 | | 115-199 |
| 0091 | 22 | | GA | | 70-0 | 29-11-21 | | D40016J | | 11 | | D01588 | | 36 | | 001-099 |
| 0091 | 20 | | GA | | 74-0 | 29-11-21 | | D40016J | | 11 | | D01588 | | 36 | | 115-199 |
| 0092 | 22 | | GA | | 70-0 | 29-11-21 | | D40016J | | 7 | | TB0059X | D007 | BJ | | 001-099 |
| 0092 | 22 | | GA | | 69-0 | 29-11-21 | | D40016J | | 7 | | TB0059X | D007 | BJ | | 115-199 |
| 0093 | 22 | | GA | | 5-0 | 29-11-21 | | D01588 | | 35 | | TB0059X | B007 | BJ | | 001-099 |
| 0093 | 22 | | GA | | 10-0 | 29-11-21 | | D01588 | | 35 | | TB0059X | B007 | BJ | | 115-199 |
| 0094 | 22 | | GA | | 5-0 | 29-11-21 | | D01588 | | 34 | | TB0059X | C007 | BJ | | 001-099 |
| 0094 | 22 | | GA | | 10-0 | 29-11-21 | | D01588 | | 34 | | TB0059X | C007 | BJ | | 115-199 |
| 0095 | 20 | | GA | | 43-0 | 29-11-22 | | D40004J | | 42 | | D41776P | | 30 | | 001-099 |
| 0095 | 20 | | GA | | 42-0 | 29-11-22 | | D40004J | | 42 | | D41776P | | 30 | | 115-199 |
| 0096 | 20 | | GA | | 42-0 | 29-11-22 | | D40004J | | 14 | | D42096P | | 3 | | ALL |
| 0097 | 22 | | GA | | 73-0 | 26-17-11 | | D40364J | | 1 | | D41990P | | 14 | | 001-099 |
| 0097 | 20 | | GA | | 73-0 | 26-17-11 | | D40364J | | 1 | | D41990P | | 14 | | 115-199 |
| 0098 | 22 | | GA | | 45-0 | 78-34-21 | | D42014P | | 21 | | TB0158Y | A002 | BJ | | 001-099 |
| 0098 | 22 | | GA | | 46-0 | 78-34-21 | | D42014P | | 21 | | TB0058Y | A006 | BJ | | 115-199 |
| 0099 | 22 | | GA | | 8-0 | 77-12-42 | | D41990P | | 12 | | D42010P | | 20 | | ALL |
| 0102 | 22 | | GA | | 41-0 | 76-11-12 | | D40899P | | 4 | | D42010P | | 4 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | 286N4236 | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0102 | 22 | | GA | | 42-0 | 76-11-12 | D40899P | | 4 | | D42010P | | 4 | | 115-199 |
| 0103 | 22 | | GA | | 41-0 | 76-11-12 | D40899P | | 20 | | D42010P | | 3 | | 001-099 |
| 0103 | 22 | | GA | | 42-0 | 76-11-12 | D40899P | | 20 | | D42010P | | 3 | | 115-199 |
| 0105 | 20 | | GA | | 7-0 | 73-21-21 | D04064 | | 18 | | GD02170 | DC.. | E | | 001-009, 115-199 |
| 0105 | 20 | | GA | | 5-0 | 73-21-21 | D04064 | | 18 | | GD02170 | DC.. | E | | 010-099 |
| 0106 | 20 | | GA | | 7-0 | 73-21-21 | D04064 | | 23 | | GD02171 | ST.. | E | | 001-009, 115-199 |
| 0106 | 20 | | GA | | 5-0 | 73-21-21 | D04064 | | 23 | | GD02171 | ST.. | E | | 010-099 |
| 0108 | 18 | | GA | | 50-0 | 73-21-22 | D04062 | | 7 | | D06402 | | 18 | 18 | 001-099 |
| 0108 | 18 | | GA | | 51-0 | 73-21-22 | D04062 | | 7 | | D06402 | | 18 | 18 | 115-199 |
| 0109 | 24 | | GK | | 38-0 | 73-21-22 | D42010P | | 25 | | SM00101 | | 9 | | 001-099 |
| 0109 | 24 | | GK | | 37-0 | 73-21-22 | D42010P | | 25 | | SM00101 | | 9 | | 115-199 |
| 0110 | 18 | | GA | | 45-0 | 73-21-22 | D06402 | | 17 | 18 | D41776P | | 18 | 18 | 001-099 |
| 0110 | 18 | | GA | | 45-0 | 73-21-22 | D41776P | | 18 | 18 | D06402 | | 17 | 18 | 115-199 |
| 0111 | 24 | | GK | | 20-0 | 73-21-22 | D41776P | | 19 | | SM00002 | | 9 | | 001-099 |
| 0111 | 24 | | GK | | 20-0 | 73-21-22 | D41776P | | 19 | | SM00008 | | 9 | | 115-199 |
| 0112 | 24 | | GK | | 45-0 | 73-21-22 | D06402 | | 21 | | D41776P | | 20 | | 001-099 |
| 0112 | 24 | | GK | | 45-0 | 73-21-22 | D41776P | | 20 | | D06402 | | 21 | | 115-199 |
| 0113 | 24 | | GK | | 26-0 | 73-21-22 | D42096P | | 10 | | D04062 | | 36 | | 001-099 |
| 0113 | 24 | | GK | | 28-0 | 73-21-22 | D04062 | | 36 | | D42096P | | 10 | | 115-199 |
| 0114 | 24 | | GK | | 32-0 | 73-21-22 | D41990P | | 18 | | D04062 | | 33 | | 001-099 |
| 0114 | 24 | | GK | | 33-0 | 73-21-22 | D04062 | | 33 | | D41990P | | 18 | | 115-199 |
| 0115 | 24 | | GK | | 32-0 | 73-21-22 | D41990P | | 19 | | D04062 | | 17 | | 001-099 |
| 0115 | 24 | | GK | | 33-0 | 73-21-22 | D04062 | | 17 | | D41990P | | 19 | | 115-199 |
| 0116 | 24 | | GK | | 20-0 | 74-31-21 | D41776P | | 24 | | D42010P | | 16 | | 001-099 |
| 0116 | 24 | | GK | | 33-0 | 73-21-22 | D04062 | | 34 | | D41990P | | 20 | | 115-199 |
| 0117 | 24 | | GK | | 32-0 | 73-21-22 | D41990P | | 21 | | D04062 | | 18 | | 001-099 |
| 0117 | 24 | | GK | | 33-0 | 73-21-22 | D04062 | | 18 | | D41990P | | 21 | | 115-199 |
| 0118 | 24 | | GK | | 32-0 | 73-21-22 | D41990P | | 22 | | D04062 | | 19 | | 001-099 |
| 0118 | 24 | | GK | | 33-0 | 73-21-22 | D04062 | | 19 | | D41990P | | 22 | | 115-199 |
| 0119 | 24 | | GK | | 32-0 | 73-21-22 | D41990P | | 23 | | D04062 | | 35 | | 001-099 |
| 0119 | 24 | | GK | | 33-0 | 73-21-22 | D04062 | | 35 | | D41990P | | 23 | | 115-199 |
| 0120 | 20 | | GA | | 7-0 | 73-21-22 | D04064 | | 19 | | GD02170 | DC.. | E | | 001-009, 115-199 |
| 0120 | 20 | | GA | | 5-0 | 73-21-22 | D04064 | | 19 | | GD02170 | DC.. | E | | 010-099 |
| 0121 | 16 | | GA | | 55-0 | 75-31-11 | SM00001 | | 9 | | D40016J | | 9 | | ALL |
| 0122 | 16 | | GA | | 55-0 | 75-31-11 | SM00005 | | 9 | | D40016J | | 17 | | 001-099 |
| 0122 | 16 | | GA | | 54-0 | 75-31-11 | SM00004 | | 9 | | D40016J | | 17 | | 115-199 |
| 0123 | 24 | | GK | | 45-0 | 31-51-33 | D03498 | | 21 | | D42014P | | 8 | | 001-099 |
| 0123 | 24 | | GK | | 46-0 | 31-51-33 | D03498 | | 21 | | D42014P | | 8 | | 115-199 |
| 0124 | 20 | | GA | | 5-0 | 21-25-11 | D03498 | | 10 | | GD00742 | DC.. | 2 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | 286N4236 | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0125 | 22 | | GA | | 20-0 | 33-16-51 | D03498 | | 4 | | TB0100Y | A010 | BJ | | ALL |
| 0126 | 22 | | GA | | 5-0 | 33-16-61 | D03498 | | 3 | | TB0058Y | C014 | BJ | | 001-099 |
| 0126 | 22 | | GA | | 6-0 | 33-16-61 | D03498 | | 3 | | TB0058Y | C014 | BJ | | 115-199 |
| 0127 | 22 | | GA | | 5-0 | 29-11-21 | D01588 | | 18 | | TB0059X | A008 | BJ | | 001-099 |
| 0127 | 22 | | GA | | 10-0 | 29-11-21 | D01588 | | 18 | | TB0059X | A008 | BJ | | 115-199 |
| 0128 | 22 | | GA | | 43-0 | 29-11-21 | D01588 | | 17 | | D42010P | 23 | | | 001-099 |
| 0128 | 22 | | GA | | 48-0 | 29-11-21 | D01588 | | 17 | | D42010P | 23 | | | 115-199 |
| 0129 | 24 | | GK | | 20-0 | 76-11-12 | D41776P | | 31 | | D42010P | 18 | | | ALL |
| 0130 | 24 | | GK | | 20-0 | 76-11-12 | D41776P | | 32 | | D42010P | 17 | | | ALL |
| 0131 | 22 | | GA | | 23-0 | SPARE | D41946P | | 31 | | D41776P | 33 | | | ALL |
| 0132 | 22 | | GA | | 5-0 | 26-11-21 | D01588 | | 24 | | GD00742 | ST.. | 2 | | 001-099 |
| 0132 | 20 | | GA | | 10-0 | 26-11-21 | D01588 | | 24 | | GD00742 | ST.. | 2 | | 115-199 |
| 0133 | 22 | | GA | | 29-0 | 26-16-11 | D41946P | | 2 | | D03498 | 12 | | | 001-099 |
| 0133 | 22 | | GA | | 28-0 | 26-16-11 | D41946P | | 2 | | D03498 | 12 | | | 115-199 |
| 0134 | 22 | | GA | | 24-0 | SPARE | D41946P | | 40 | | D42010P | CAP | Y | | 001-002 |
| 0134 | 22 | | GA | | 24-0 | SPARE | D41946P | | 40 | | D42010P | 13 | | | 003-099 |
| 0134 | 22 | | GA | | 25-0 | SPARE | D41946P | | 40 | | D42010P | CAP | Y | | 115-199 |
| 0135 | 22 | | GA | | 23-0 | 26-16-11 | D41946P | | 16 | | D41776P | 34 | | | ALL |
| 0136 | 22 | | GA | | 23-0 | 26-16-11 | D41946P | | 28 | | D41776P | 35 | | | ALL |
| 0137 | 22 | | GA | | 23-0 | 26-22-21 | D41946P | | 39 | | D41776P | 36 | | | 001-099 |
| 0137 | 22 | | GA | | 41-0 | 26-22-21 | D03498 | | 19 | | D41776P | 36 | | | 115-199 |
| 0138 | 20 | | GA | | 22-0 | 26-23-11 | D03498 | | 17 | | D44106P | 3 | | | 001-099 |
| 0138 | 20 | | GA | | 24-0 | 26-23-11 | D03498 | | 17 | | D44106P | 3 | | | 115-199 |
| 0139 | 20 | | GA | | 22-0 | 26-23-11 | D03498 | | 20 | | D44104P | 3 | | | 001-099 |
| 0139 | 20 | | GA | | 23-0 | 26-23-11 | D03498 | | 20 | | D44104P | 3 | | | 115-199 |
| 0140 | 20 | | GA | | 22-0 | 26-23-11 | D03498 | | 16 | | D44106P | 4 | | | 001-099 |
| 0140 | 20 | | GA | | 24-0 | 26-23-11 | D03498 | | 16 | | D44106P | 4 | | | 115-199 |
| 0141 | 20 | | GA | | 29-0 | 26-23-11 | D03498 | | 15 | | D41946P | 32 | | | 001-099 |
| 0141 | 20 | | GA | | 28-0 | 26-23-11 | D03498 | | 15 | | D41946P | 32 | | | 115-199 |
| 0142 | 20 | | GA | | 29-0 | 26-23-11 | D03498 | | 5 | | D41946P | 33 | | | 001-099 |
| 0142 | 20 | | GA | | 28-0 | 26-23-11 | D03498 | | 5 | | D41946P | 33 | | | 115-199 |
| 0143 | 20 | | GA | | 29-0 | 26-23-11 | D03498 | | 22 | | D41946P | 34 | | | 001-099 |
| 0143 | 20 | | GA | | 28-0 | 26-23-11 | D03498 | | 22 | | D41946P | 34 | | | 115-199 |
| 0144 | 20 | | GA | | 5-0 | 26-23-11 | D03498 | | 23 | | GD01650 | DC.. | 2 | | ALL |
| 0145 | 20 | | GA | | 25-0 | 26-21-11 | D41946P | | 36 | | SM00006 | | 9 | | 001-099 |
| 0145 | 20 | | GA | | 22-0 | 26-21-11 | D41946P | | 36 | | SM00006 | | 9 | | 115-199 |
| 0146 | 20 | | GA | | 25-0 | 26-21-11 | D41946P | | 35 | | SM00007 | | 9 | | 001-099 |
| 0146 | 20 | | GA | | 22-0 | 26-21-11 | D41946P | | 35 | | SM00007 | | 9 | | 115-199 |
| 0147 | 22 | | GA | | 23-0 | 26-21-11 | D41946P | | 37 | | D41776P | 8 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | 286N4236 | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0148 | 22 | GA | | | 29-0 | 26-22-21 | D03498 | | | 19 | D41946P | | | 17 | 001-099 |
| 0149 | 22 | GA | | | 77-0 | 29-22-11 | D40364J | | | 7 | D41950P | | | 7 | 001-099 |
| 0149 | 22 | GA | | | 78-0 | 29-22-11 | D40364J | | | 7 | D41950P | | | 7 | 115-199 |
| 0150 | 22 | GA | | | 77-0 | 29-22-11 | D40364J | | | 8 | D41950P | | | 8 | 001-099 |
| 0150 | 22 | GA | | | 78-0 | 29-22-11 | D40364J | | | 8 | D41950P | | | 8 | 115-199 |
| 0151 | 22 | GA | | | 75-0 | 32-41-11 | D40364J | | | 6 | D42014P | | | 12 | 001-099 |
| 0151 | 22 | GA | | | 76-0 | 32-41-11 | D40364J | | | 6 | D42014P | | | 12 | 115-199 |
| 0152 | 20 | GA | | | 55-0 | SPARE | D40004J | | | 43 | D42014P | | | 14 | 115-199 |
| 0153 | 24 | GK | | | 31-0 | SPARE | D41950P | | | 15 | D42014P | | | 15 | 001-099 |
| 0153 | 24 | GK | | | 34-0 | SPARE | D41950P | | | 15 | D42014P | | | 15 | 115-199 |
| 0154 | 20 | GA | | | 75-0 | 32-42-11 | D42014P | | | 13 | D40364J | | | 10 | 001-099 |
| 0154 | 20 | GA | | | 76-0 | 32-42-11 | D42014P | | | 13 | D40364J | | | 10 | 115-199 |
| 0155 | 22 | GA | | | 28-0 | 26-18-11 | D41990P | | | 44 | D41946P | | | 44 | ALL |
| 0156 | 22 | GA | | | 28-0 | 26-18-11 | D41990P | | | 45 | D41946P | | | 45 | ALL |
| 0157 | 22 | GA | | | 28-0 | 26-18-11 | D41990P | | | 46 | D41946P | | | 46 | ALL |
| 0158 | 22 | GA | | | 28-0 | 26-18-11 | D41990P | | | 47 | D41946P | | | 47 | ALL |
| 0159 | 22 | GA | | | 28-0 | 26-18-11 | D41990P | | | 48 | D41946P | | | 48 | ALL |
| 0160 | 22 | GA | | | 28-0 | 26-18-11 | D41990P | | | 49 | D41946P | | | 49 | ALL |
| 0161 | 22 | GA | | | 28-0 | 26-18-11 | D41990P | | | 50 | D41946P | | | 50 | ALL |
| 0162 | 22 | GA | | | 28-0 | 26-18-11 | D41990P | | | 51 | D41946P | | | 51 | ALL |
| 0163 | 24 | GK | | | 5-0 | 21-44-11 | D03498 | | | 8 | TB0058X | B012 | BJ | | 001-099 |
| 0163 | 24 | GK | | | 6-0 | 21-44-11 | D03498 | | | 8 | TB0058X | B012 | BJ | | 115-199 |
| 0164 | 24 | GK | | | 5-0 | 21-44-11 | D03498 | | | 6 | TB0058X | C012 | BJ | | 001-099 |
| 0164 | 24 | GK | | | 6-0 | 21-44-11 | D03498 | | | 6 | TB0058X | C012 | BJ | | 115-199 |
| 0165 | 20 | GA | | | 43-0 | 29-11-22 | D40004J | | | 8 | D41776P | | | 28 | 001-099 |
| 0165 | 20 | GA | | | 42-0 | 29-11-22 | D40004J | | | 8 | D41776P | | | 28 | 115-199 |
| 0166 | 22 | GA | | | 14-0 | 26-15-12 | D41950P | | | 3 | D41946P | | | 27 | 001-099 |
| 0166 | 22 | GA | | | 16-0 | 26-15-12 | D41950P | | | 3 | D41946P | | | 27 | 115-199 |
| 0167 | 22 | GA | | | 14-0 | 26-15-12 | D41950P | | | 4 | D41946P | | | 29 | 001-099 |
| 0167 | 22 | GA | | | 16-0 | 26-15-12 | D41950P | | | 4 | D41946P | | | 29 | 115-199 |
| 0168 | 20 | GA | | | 16-0 | 26-15-12 | D41950P | | | 5 | D41946P | | | 38 | 115-199 |
| 0172 | 20 | GA | | | 27-0 | 26-22-21 | D41950P | | | 6 | D42096P | | | 6 | 001-099 |
| 0173 | 20 | GA | | | 14-0 | 26-22-21 | D41950P | | | 5 | D41946P | | | 20 | 001-099 |
| 0175 | 12 | GA | | | 12-4 | 29-21-31 | D42096P | | | 16 | SP01526 | | | 9 | 001-099 |
| 0175 | 12 | GA | | | 4-4 | 29-21-31 | D42096P | | | 16 | SP01526 | | | 9 | 115-199 |
| 0180 | 20 | GA | | | 27-0 | 26-22-21 | D42096P | | | 11 | D41950P | | | 11 | 001-099 |
| 0181 | 12 | GA | | | 61-3 | 29-21-31 | D42096P | | | 14 | SM00003 | | | 9 | 001-099 |
| 0181 | 12 | GA | | | 60-5 | 29-21-31 | D42096P | | | 14 | SM00003 | | | 9 | 115-199 |
| 0183 | 20 | GA | | | 5-0 | 36-11-21 | D01588 | | | 14 | TB0058X | B010 | BJ | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | To | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | 286N4236 | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 0183 | 20 | | GA | | 11-0 | 36-11-21 | D01588 | | 14 | | TB0058X | B010 | BJ | | 115-199 |
| 0184 | 20 | | GA | | 5-0 | 36-11-21 | D01588 | | 31 | | TB0058X | A010 | BJ | | 001-099 |
| 0184 | 20 | | GA | | 11-0 | 36-11-21 | D01588 | | 31 | | TB0058X | A010 | BJ | | 115-199 |
| 0185 | 20 | | GA | | 70-0 | 28-22-21 | D40016J | | 15 | | TB0158Y | A001 | BJ | | 001-099 |
| 0185 | 20 | | GA | | 69-0 | 28-22-21 | D40016J | | 15 | | TB0158Y | A001 | BJ | | 115-199 |
| 0186 | 20 | | GA | | 20-0 | 28-22-21 | D40899P | | 19 | | TB0158Y | A001 | BJ | | ALL |
| 0187 | 22 | | GA | | 1-0 | 26-11-21 | TB0159A | C004 | 2 | | TB0159A | C003 | 2 | | ALL |
| 0188 | 22 | | GA | | 20-0 | 26-11-21 | D40899P | | 1 | | TB0159A | A005 | 2 | | ALL |
| 0189 | 20 | | GA | | 75-0 | 32-42-11 | D42014P | | 18 | | D40364J | | 11 | | 001-099 |
| 0189 | 20 | | GA | | 76-0 | 32-42-11 | D42014P | | 18 | | D40364J | | 11 | | 115-199 |
| 0190 | 20 | | GA | | 1-6 | 73-21-22 | D04736 | | | AE | GD02902 | ST.. | E | | 001-099 |
| 0190 | 20 | | GA | | 4-0 | 73-21-22 | D04736 | | | AE | GD01976 | ST.. | E | | 115-199 |
| 0191 | 16 | | GA | | 1-0 | 75-31-11 | D04064 | | 16 | | SM00001 | | 9 | | ALL |
| 0192 | 16 | | GA | | 5-0 | 75-31-11 | SP01042 | | | 9 | SM00001 | | 9 | | ALL |
| 0193 | 16 | | GA | | 29-0 | 75-31-11 | SP01040 | | | 9 | D42010P | 24 | 16 | | 001-099 |
| 0193 | 16 | | GA | | 32-0 | 75-31-11 | SP01040 | | | 9 | D42010P | 24 | 16 | | 115-199 |
| 0195 | 22 | | GA | | 24-0 | 26-11-21 | D41946P | | 42 | | D42010P | 19 | | | 001-099 |
| 0195 | 22 | | GA | | 25-0 | 26-11-21 | D41946P | | 42 | | D42010P | 19 | | | 115-199 |
| 0196 | 22 | | GA | | 20-0 | 77-12-42 | D42096P | | 5 | | D42010P | 15 | | | ALL |
| 0204 | 24 | | GK | | 10-0 | 73-21-22 | D06402 | | 23 | | SM00101 | | 9 | | 001-099 |
| 0204 | 24 | | GK | | 11-0 | 73-21-22 | D06402 | | 23 | | SM00101 | | 9 | | 115-199 |
| 0205 | 24 | | GK | | 10-0 | 73-21-22 | D06402 | | 16 | | SM00101 | | 9 | | 001-099 |
| 0205 | 24 | | GK | | 11-0 | 73-21-22 | D06402 | | 16 | | SM00101 | | 9 | | 115-199 |
| 0211 | 22 | | GA | | 9-0 | 33-13-32 | D06402 | | 1 | | TB0116Z | 22 | BJ | | 001-099 |
| 0211 | 22 | | GA | | 9-0 | 33-13-32 | D06402 | | 1 | | TB0115Z | 13 | BJ | | 115-199 |
| 0212 | 22 | | GA | | 6-0 | 73-21-22 | D06402 | | 15 | | GD00608 | DC.. | 2 | | ALL |
| 0213 | 22 | | GA | | 9-0 | 33-13-32 | D06402 | | 2 | | TB0115Z | 14 | BJ | | ALL |
| 0214 | 22 | | GA | | 7-0 | 33-16-62 | D06402 | | 3 | | TB0114Z | 22 | BJ | | 001-099 |
| 0214 | 22 | | GA | | 9-0 | 33-16-62 | D06402 | | 3 | | TB0114Z | 22 | BJ | | 115-199 |
| 0215 | 22 | | GA | | 9-0 | 33-16-52 | D06402 | | 4 | | TB0116Z | 10 | BJ | | ALL |
| 0220 | 22 | | GA | | 51-0 | SPARE | D40004J | | 18 | | D41990P | 16 | | | 001-099 |
| 0221 | 20 | | GA | | 43-0 | SPARE | D40004J | | 41 | | D41776P | 12 | | | 001-099 |
| 0222 | 22 | | GA | | 47-0 | 26-17-11 | D03492 | | 13 | | D41990P | 13 | | | ALL |
| 0223 | 22 | | GA | | 6-0 | 26-17-11 | D03492 | | 12 | | GD01650 | DC.. | 2 | | 001-099 |
| 0223 | 20 | | GA | | 5-0 | 26-17-11 | D03492 | | 12 | | GD01650 | DC.. | 2 | | 115-199 |
| 0224 | 16 | | HL | | 0-6 | 29-21-31 | D04086 | | 1 | | SM00004 | | 9 | | 001-099 |
| 0225 | 16 | | HL | | 0-12 | 29-21-31 | D04086 | | 2 | | GD02284 | DC.. | E | | 001-099 |
| 0225 | 16 | | GA | | 1-0 | 75-31-11 | D04064 | | 15 | | SM00004 | | 9 | | 115-199 |
| 0226 | 18 | | HL | | 2-0 | 29-21-31 | D04086 | | 3 | | GD02285 | ST.. | E | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | | 286N4236 | | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | |
| 0226 | 16 | GA | | | 5-0 | 75-31-11 | SP01044 | | 9 | | SM00004 | | 9 | | 115-199 |
| 0227 | 24 | GK | | | 44-0 | 73-21-21 | D42010P | 21 | | | TB0114X | A014 | BJ | | 001-099 |
| 0227 | 24 | GK | | | 43-0 | 73-21-21 | D42010P | 21 | | | TB0159X | B001 | BJ | | 115-199 |
| 0228 | 24 | GK | | | 28-0 | 73-21-22 | D42010P | 26 | | | D04062 | 5 | | | 001-099 |
| 0228 | 24 | GK | | | 30-0 | 73-21-22 | D42010P | 26 | | | D04062 | 5 | | | 115-199 |
| 0229 | 24 | GK | | | 46-0 | 73-21-22 | D06402 | 19 | | | D42010P | 27 | | | 001-099 |
| 0229 | 24 | GK | | | 47-0 | 73-21-22 | D42010P | 27 | | | D06402 | 19 | | | 115-199 |
| 0230 | 24 | GK | | | 46-0 | 73-21-22 | D06402 | 22 | | | D42010P | 28 | | | 001-099 |
| 0230 | 24 | GK | | | 47-0 | 73-21-22 | D42010P | 28 | | | D06402 | 22 | | | 115-199 |
| 0231 | 20 | GA | | | 47-0 | 36-11-21 | D40274J | 7 | | | D42010P | 35 | | | 001-099 |
| 0231 | 20 | GA | | | 47-0 | 36-11-21 | D40274J | 7 | | | D42010P | 16 | | | 115-199 |
| 0232 | 20 | GA | | | 8-0 | 29-11-22 | D41776P | 29 | | | D42096P | 6 | | | 115-199 |
| 0233 | 24 | GK | | | 20-0 | 73-21-22 | D42096P | 9 | | | SM00002 | | 9 | | 001-099 |
| 0233 | 24 | GK | | | 20-0 | 73-21-22 | D42096P | 9 | | | SM00008 | | 9 | | 115-199 |
| 0234 | 24 | GK | | | 1-0 | 73-21-22 | D42010P | 30 | | | SM00002 | | 9 | | 001-099 |
| 0234 | 24 | GK | | | 1-0 | 73-21-22 | D42010P | 30 | | | SM00008 | | 9 | | 115-199 |
| 0235 | 18 | GA | | | 28-0 | 73-21-22 | D42010P | 29 | 18 | | D04064 | 17 | | | 001-099 |
| 0235 | 18 | GA | | | 31-0 | 73-21-22 | D42010P | 29 | 18 | | D04064 | 17 | | | 115-199 |
| 0236 | 20 | GA | | | 48-0 | SPARE | D40016J | 27 | | | D42010P | 36 | | | 001-099 |
| 0236 | 16 | HL | | | 0-6 | 29-21-31 | D04086 | 1 | | | SM00005 | | 9 | | 115-199 |
| 0237 | 16 | GA | | | 1-0 | 75-31-11 | D04064 | 15 | | | SM00005 | | 9 | | 001-099 |
| 0237 | 16 | HL | | | 0-12 | 29-21-31 | D04086 | 2 | | | GD02284 | DC.. | E | | 115-199 |
| 0238 | 16 | GA | | | 5-0 | 75-31-11 | SP01044 | | 9 | | SM00005 | | 9 | | 001-099 |
| 0238 | 18 | HL | | | 2-0 | 29-21-31 | D04086 | 3 | | | GD02285 | ST.. | E | | 115-199 |
| 0246 | 20 | GA | | | 19-0 | 26-21-11 | D44106P | 1 | | | SM00007 | | 9 | | 001-099 |
| 0246 | 20 | GA | | | 18-0 | 26-21-11 | D44106P | 1 | | | SM00007 | | 9 | | 115-199 |
| 0248 | 22 | GA | | | 50-0 | 76-11-12 | D41258P | 3 | | | D40004J | 27 | | | 001-099 |
| 0248 | 22 | GA | | | 53-0 | 76-11-12 | D41258P | 3 | | | D40004J | 27 | | | 115-199 |
| 0249 | 22 | GA | | | 50-0 | 76-11-12 | D41258P | 4 | | | D40016J | 1 | | | 001-099 |
| 0249 | 22 | GA | | | 51-0 | 76-11-12 | D41258P | 4 | | | D40016J | 1 | | | 115-199 |
| 0251 | 22 | GA | | | 44-0 | 76-11-12 | D40899P | 13 | | | D41258P | 2 | | | 001-099 |
| 0251 | 22 | GA | | | 46-0 | 76-11-12 | D40899P | 13 | | | D41258P | 2 | | | 115-199 |
| 0252 | 22 | GA | | | 45-0 | 76-11-12 | D01588 | 6 | | | D41258P | 1 | | | 001-099 |
| 0252 | 22 | GA | | | 51-0 | 76-11-12 | D01588 | 6 | | | D41258P | 1 | | | 115-199 |
| 0255 | 16 | GA | | | 8-0 | 75-31-11 | D42014P | 16 | 16 | | SP01264 | | 9 | | 001-099 |
| 0255 | 16 | GA | | | 9-0 | 75-31-11 | D42014P | 16 | 16 | | SP01264 | | 9 | | 115-199 |
| 0256 | 16 | GA | | | 8-0 | 75-31-11 | D42014P | 17 | 16 | | SM00005 | | 9 | | 001-099 |
| 0256 | 16 | GA | | | 6-0 | 75-31-11 | D42014P | 17 | 16 | | SM00004 | | 9 | | 115-199 |
| 0257 | 20 | GA | | | 1-0 | 77-21-11 | D04066 | 3 | | | D04066 | 4 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 15

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4236 | 286N4236 | | | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | |
| 2502B | 22 | | GU | AM | 56-0 | 73-21-21 | D04064 | 13 | | | D40004J | 48 | | | 001-099 |
| 2502B | 22 | | GU | AM | 57-0 | 73-21-21 | D04064 | 13 | | | D40004J | 48 | | | 115-199 |
| 2502R | 22 | | GU | AM | 0-0 | 73-21-21 | D04064 | 12 | | | D40004J | 47 | | | ALL |
| 2502Z | | | | AM | 0-0 | 73-21-21 | D04064 | | | AC | D40004J | | | AA | 001-099 |
| 2502Z | | | | AM | 0-0 | 73-21-21 | D04064 | | | AB | D40004J | | | AA | 115-199 |
| 2503B | 22 | | GU | AN | 56-0 | 73-21-21 | D04064 | 29 | | | D40004J | 50 | | | 001-099 |
| 2503B | 22 | | GU | AN | 57-0 | 73-21-21 | D04064 | 29 | | | D40004J | 50 | | | 115-199 |
| 2503R | 22 | | GU | AN | 0-0 | 73-21-21 | D04064 | 28 | | | D40004J | 49 | | | ALL |
| 2503Z | | | | AN | 0-0 | 73-21-21 | D04064 | | | AC | D40004J | | | AA | 001-099 |
| 2503Z | | | | AN | 0-0 | 73-21-21 | D04064 | | | AB | D40004J | | | AA | 115-199 |
| 2505B | 24 | | G2 | AE | 27-0 | 73-21-22 | D04062 | 12 | | | D41776P | 14 | | | 001-099 |
| 2505B | 24 | | G2 | AE | 28-0 | 73-21-22 | D04062 | 12 | | | D41776P | 14 | | | 115-199 |
| 2505R | 24 | | G2 | AE | 0-0 | 73-21-22 | D04062 | 4 | | | D41776P | 13 | | | ALL |
| 2505Z | | | | AE | 0-0 | 73-21-22 | D04062 | | | AD | D41776P | | | AB | 001-099 |
| 2505Z | | | | AE | 0-0 | 73-21-22 | D04062 | | | AC | D41776P | | | AD | 115-199 |
| 2506B | 24 | | G2 | AF | 27-0 | 73-21-22 | D41776P | 16 | | | D04062 | 26 | | | 001-099 |
| 2506B | 24 | | G2 | AP | 28-0 | 73-21-22 | D04062 | 26 | | | D41776P | 16 | | | 115-199 |
| 2506R | 24 | | G2 | AF | 0-0 | 73-21-22 | D41776P | 15 | | | D04062 | 25 | | | 001-099 |
| 2506R | 24 | | G2 | AP | 0-0 | 73-21-22 | D04062 | 25 | | | D41776P | 15 | | | 115-199 |
| 2506Z | | | | AF | 0-0 | 73-21-22 | D41776P | | | AB | D04062 | | | AD | 001-099 |
| 2506Z | | | | AP | 0-0 | 73-21-22 | D04062 | | | AC | D41776P | | | AD | 115-199 |
| 2507B | 22 | | GU | AH | 46-0 | 73-21-22 | D04736 | 1 | | | D04062 | 40 | | | 001-099 |
| 2507B | 22 | | GU | AF | 46-0 | 73-21-22 | D04062 | 40 | | | D04736 | 1 | | | 115-199 |
| 2507R | 22 | | GU | AH | 0-0 | 73-21-22 | D04736 | 2 | | | D04062 | 41 | | | 001-099 |
| 2507R | 22 | | GU | AF | 0-0 | 73-21-22 | D04062 | 41 | | | D04736 | 2 | | | 115-199 |
| 2507Z | | | | AH | 0-0 | 73-21-22 | D04736 | | | AE | D04062 | 42 | | | 001-099 |
| 2507Z | | | | AF | 0-0 | 73-21-22 | D04062 | 42 | | | D04736 | | | AE | 115-199 |
| 2508B | 24 | | G2 | AI | 27-0 | 77-12-11 | D04064 | 27 | | | D41776P | 37 | | | 001-099 |
| 2508B | 24 | | G2 | AK | 28-0 | 77-12-11 | D04064 | 27 | | | D41776P | 37 | | | 115-199 |
| 2508R | 24 | | G2 | AI | 0-0 | 77-12-11 | D04064 | 26 | | | D41776P | 38 | | | 001-099 |
| 2508R | 24 | | G2 | AK | 0-0 | 77-12-11 | D04064 | 26 | | | D41776P | 38 | | | 115-199 |
| 2508Z | | | | AI | 0-0 | 77-12-11 | D04064 | DED | | | D41776P | 39 | | | 001-099 |
| 2508Z | | | | AK | 0-0 | 77-12-11 | D04064 | DED | | | D41776P | 39 | | | 115-199 |
| 2509B | 20 | | GU | CE | 43-0 | SPARE | D40004J | 12 | | | D41776P | 40 | | | 001-099 |
| 2509R | 20 | | GU | CE | 0-0 | SPARE | D40004J | 13 | | | D41776P | 41 | | | 001-099 |
| 2509Z | | | | CE | 0-0 | SPARE | D40004J | S/R | | | D41776P | 9 | | | 001-099 |
| 2510B | 20 | | GU | CF | 48-0 | SPARE | D40004J | 38 | | | D42010P | 37 | | | 001-099 |
| 2510R | 20 | | GU | CF | 0-0 | SPARE | D40004J | 39 | | | D42010P | 38 | | | 001-099 |
| 2510Z | | | | CF | 0-0 | SPARE | D40004J | S/R | | | D42010P | 39 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 17

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | Description | From | To | | | | | | | | | | | | |
|------------|-------------|--|------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|--|
| Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | | |
| W4236 | 286N4236 | E/E SHELF DISC TO RIGHT WING BODY/ WHEEL WELL DISC (continued) | | | | | | | | | | | | | | |
| 5003Z | | | AW | 0-0 | 31-31-23 | D42014P | 11 | | | D04062 | DED | | | 115-199 | | |
| A-A | | | | 0-0 | 75-31-11 | S10380 | 1 | | | SP01040 | | 9 | | ALL | | |
| A-B | | | | 0-0 | 75-31-11 | S10380 | 4 | | | SP01040 | | 9 | | ALL | | |
| A-C | | | | 0-0 | 75-31-11 | S10380 | 3 | | | SP01042 | | 9 | | ALL | | |
| A-D | | | | 0-0 | 75-31-11 | S10380 | 5 | | | SP01044 | CAP | Y | | ALL | | |
| A-E | | | | 0-0 | 75-31-11 | S10380 | 7 | | | SP01264 | | 9 | | ALL | | |
| A-F | | | | 0-0 | 75-31-11 | S10380 | 8 | | | GD03122 | DC.. | E | | ALL | | |
| A-G | | | | 0-0 | 75-31-11 | S10380 | 6 | | | SP01044 | | 9 | | ALL | | |
| A-H | | | | 0-0 | 75-31-11 | S10380 | 2 | | | SP01040 | CAP | Y | | ALL | | |
| FRAA | | | | 0-0 | 73-21-21 | D40004J | 51 | | | D40004J | | | AA | ALL | | |
| FRAB | | | | 0-0 | 73-21-22 | D41776P | | | AB | D41776P | 17 | | | 001-099 | | |
| FRAB | | | | 0-0 | 73-21-21 | D04064 | 20 | | | D04064 | | | AB | 115-199 | | |
| FRAC | | | | 0-0 | 73-21-21 | D04064 | 20 | | | D04064 | | | AC | 001-099 | | |
| FRAC | | | | 0-0 | 73-21-22 | D04062 | 3 | | | D04062 | | | AC | 115-199 | | |
| FRAD | | | | 0-0 | 73-21-22 | D04062 | 3 | | | D04062 | | | AD | 001-099 | | |
| FRAD | | | | 0-0 | 73-21-22 | D41776P | 17 | | | D41776P | | | AD | 115-199 | | |
| FRAT | | | | 0-0 | 78-34-61 | D40899P | | | AT | GD02519 | ST.. | 2 | | 001-002, 115-199 | | |
| FRAT | | | | 0-0 | 78-34-61 | D42010P | 40 | | | D42010P | | | AT | 003-099 | | |
| YAAA | | | | 0-0 | 78-34-21 | D40274J | S/R | | | GD03094 | ST.. | E | | 001-099 | | |
| YAAA | | | | 0-0 | 29-11-22 | GD03094 | ST.. | E | | D40004J | S/R | | | 115-199 | | |
| YAAB | | | | 0-0 | 75-31-11 | D40004J | S/R | | | GD03094 | ST.. | E | * | 001-099 | | |
| YAAB | | | | 0-0 | 29-11-21 | GD03094 | ST.. | E | * | D40016J | S/R | | | 115-199 | | |
| YAAC | | | | 0-0 | 26-11-21 | D40016J | S/R | | | GD03094 | ST.. | E | * | 001-099 | | |
| YAAC | | | | 0-0 | 78-34-21 | GD03094 | ST.. | E | * | D40274J | S/R | | | 115-199 | | |
| W4238 | 286N4238 | E/E SHELF DISC TO RIGHT WING BODY DISC | | | | | | | | | | | | | | |
| 0001 | 18 | GA | | 70-0 | 73-21-21 | D40020J | 34 | | | TB0114F | A005 | 2 | | 001-099 | | |
| 0001 | 18 | GA | | 70-0 | 73-21-21 | D40020J | 34 | | | TB0101F | A005 | 2 | | 115-199 | | |
| 0002 | 18 | GA | | 70-0 | 73-21-21 | D40020J | 2 | | | TB0114F | A006 | 2 | | 001-099 | | |
| 0002 | 18 | GA | | 68-0 | 73-21-21 | D40020J | 2 | | | TB0159F | A006 | 2 | | 115-199 | | |
| 0003 | 18 | GA | | 41-0 | 73-21-22 | D40020J | 7 | | | D41788P | 19 | 18 | | 115-199 | | |
| 0004 | 18 | GA | | 70-0 | 73-21-22 | D40020J | 8 | | | TB0101F | C005 | 2 | | 115-199 | | |
| 0006 | 18 | GA | | 48-0 | 75-31-11 | D40020J | 33 | | | D41998P | 1 | | | 001-099 | | |
| 0006 | 18 | GA | | 49-0 | 75-31-11 | D40020J | 33 | | | D41998P | 1 | | | 115-199 | | |
| 0007 | 16 | GA | | 48-0 | 75-31-11 | D40020J | 31 | | | D41998P | 2 | | | 001-099 | | |
| 0007 | 16 | GA | | 49-0 | 75-31-11 | D40020J | 31 | | | D41998P | 2 | | | 115-199 | | |
| 0008 | 22 | GA | | 45-0 | 75-31-11 | D40020J | 13 | | | D41788P | 2 | | | 001-099 | | |
| 0008 | 22 | GA | | 41-0 | 75-31-11 | D40020J | 13 | | | D41788P | 2 | | | 115-199 | | |
| 0009 | 20 | GA | | 45-0 | 75-31-11 | D40020J | 1 | | | D41788P | 3 | | | 001-099 | | |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4238 | 286N4238 | | | | E/E SHELF DISC TO RIGHT WING BODY DISC (continued) | | | | | | | | | | | |
| 0009 | 20 | | GA | | 41-0 | 75-31-11 | | D40020J | | 1 | | D41788P | | 3 | | 115-199 |
| 0010 | 20 | | GA | | 4-0 | 33-13-51 | | D40784P | | 4 | | TB0100X | C002 | BJ | | 115-199 |
| 0013 | 18 | | GA | | 70-0 | 73-21-22 | | D40020J | | 8 | | TB0114F | C005 | 2 | | 001-099 |
| 0014 | 18 | | GA | | 45-0 | 73-21-22 | | D40020J | | 7 | | D41788P | 19 | 18 | | 001-099 |
| 0015 | 24 | | GK | | 43-0 | SPARE | | D40784P | | 2 | | D41998P | | 5 | | 115-199 |
| 0016 | 22 | | GA | | 39-0 | 32-44-11 | | D40784P | | 3 | | D41788P | | 7 | | 115-199 |
| 0022 | 24 | | GK | | 1-0 | 77-31-11 | | D41788P | | 17 | | D41788P | | 25 | | ALL |
| 0023 | 24 | | GK | | 25-0 | 73-21-22 | | D41998P | | 8 | | D41784P | | 1 | | 001-099 |
| 0023 | 24 | | GK | | 13-0 | 73-21-22 | | D41998P | | 8 | | D41784P | | 1 | | 115-199 |
| 0024 | 24 | | GK | | 23-0 | 73-21-22 | | D41788P | | 24 | | D41784P | | 2 | | 001-099 |
| 0024 | 24 | | GK | | 25-0 | 73-21-22 | | D41788P | | 24 | | D41784P | | 2 | | 115-199 |
| 0025 | 22 | | GA | | 2-0 | 77-31-11 | | D40020J | | 26 | | D40020J | | 11 | | ALL |
| 0026 | 22 | | GA | | 2-0 | 77-31-11 | | D40020J | | 10 | | D40020J | | 9 | | ALL |
| 0027 | 22 | | GA | | 2-0 | 77-31-11 | | D40020J | | 22 | | D40020J | | 39 | | ALL |
| 1002 | 20 | | GE | T | 48-0 | 77-11-11 | | D40020J | | 3 | | D41998P | | 7 | | 001-099 |
| 1002 | 20 | | GE | T | 49-0 | 77-11-11 | | D40020J | | 3 | | D41998P | | 7 | | 115-199 |
| 1002Z | | | | T | 0-0 | 77-11-11 | | D40020J | S/R | | | GD03624 | ST.. | E | | 001-099 |
| 1002Z | | | | T | 0-0 | 77-11-11 | | D40020J | S/R | | | GD03622 | ST.. | E | | 115-199 |
| 2001B | 20 | | GB | AA | 50-0 | 22-33-11 | | D40020J | | 14 | | D41784P | | 6 | | 001-099 |
| 2001B | 20 | | GB | AA | 55-0 | 22-33-11 | | D40020J | | 14 | | D41784P | | 6 | | 115-199 |
| 2001R | 20 | | GB | AA | 0-0 | 22-33-11 | | D40020J | | 16 | | D41784P | | 5 | | ALL |
| 2002B | 20 | | GB | AB | 50-0 | 22-33-11 | | D40020J | | 35 | | D41784P | | 8 | | 001-099 |
| 2002B | 20 | | GB | AB | 55-0 | 22-33-11 | | D40020J | | 35 | | D41784P | | 8 | | 115-199 |
| 2002R | 20 | | GB | AB | 0-0 | 22-33-11 | | D40020J | | 6 | | D41784P | | 7 | | ALL |
| 2501B | 22 | | GU | AD | 45-0 | 77-12-31 | | D40020J | | 30 | | D41788P | | 8 | | 001-099 |
| 2501B | 22 | | GU | AD | 41-0 | 77-12-31 | | D40020J | | 30 | | D41788P | | 8 | | 115-199 |
| 2501R | 22 | | GU | AD | 0-0 | 77-12-31 | | D40020J | | 29 | | D41788P | | 9 | | ALL |
| 2501Z | | | | AD | 0-0 | 77-12-31 | | D40020J | S/R | | | D41788P | | 10 | | ALL |
| 2502B | 22 | | GU | AH | 45-0 | SPARE | | D40020J | | 21 | | D41788P | | 1 | | 001-099 |
| 2502R | 22 | | GU | AH | 0-0 | SPARE | | D40020J | | 27 | | D41788P | | 23 | | 001-099 |
| 2502Z | | | | AH | 0-0 | SPARE | | D40020J | | 28 | | D41788P | | 11 | | 001-099 |
| 2503B | 20 | | GU | AL | 48-0 | SPARE | | D40020J | | 15 | | D41998P | | 4 | | 001-099 |
| 2503R | 20 | | GU | AL | 0-0 | SPARE | | D40020J | | 18 | | D41998P | | 5 | | 001-099 |
| 2503Z | | | | AL | 0-0 | SPARE | | D40020J | | 19 | | D41998P | | 6 | | 001-099 |
| 4501R | 20 | | RJ | AE | 45-0 | 77-31-11 | | D40020J | | 40 | | D41788P | | 27 | | 001-099 |
| 4501R | 20 | | RJ | AE | 41-0 | 77-31-11 | | D40020J | | 40 | | D41788P | | 27 | | 115-199 |
| 4501W | 20 | | RJ | AE | 0-0 | 77-31-11 | | D40020J | | 25 | | D41788P | | 26 | | ALL |
| 4501Z | | | | AE | 0-0 | 77-31-11 | | D40020J | | 23 | | D41788P | | 14 | | ALL |
| 4502R | 20 | | RJ | AJ | 45-0 | 77-31-11 | | D40020J | | 42 | | D41788P | | 29 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4238 | 286N4238 | | | E/E SHELF DISC TO RIGHT WING BODY DISC (continued) | | | | | | | | | | | |
| 4502R | 20 | RJ | AJ | | 41-0 | 77-31-11 | D40020J | 42 | | | D41788P | 29 | | | 115-199 |
| 4502W | 20 | RJ | AJ | | 0-0 | 77-31-11 | D40020J | 41 | | | D41788P | 28 | | | ALL |
| 4502Z | | | AJ | | 0-0 | 77-31-11 | D40020J | 24 | | | D41788P | 16 | | | ALL |
| 5001B | 22 | GU | AC | | 45-0 | 77-11-11 | D40020J | 4 | | | D41788P | 4 | | | 001-099 |
| 5001B | 22 | GU | AC | | 41-0 | 77-11-11 | D40020J | 4 | | | D41788P | 4 | | | 115-199 |
| 5001R | 22 | GU | AC | | 0-0 | 77-11-11 | D40020J | 5 | | | D41788P | 5 | | | ALL |
| 5001Z | | | AC | | 0-0 | 77-11-11 | D40020J | S/R | | | D41788P | 6 | | | ALL |
| 5002B | 22 | GU | AK | | 45-0 | 77-11-11 | D40020J | 37 | | | D41788P | 21 | | | 001-099 |
| 5002B | 22 | GU | AK | | 41-0 | 77-11-11 | D40020J | 37 | | | D41788P | 21 | | | 115-199 |
| 5002R | 22 | GU | AK | | 0-0 | 77-11-11 | D40020J | 36 | | | D41788P | 20 | | | ALL |
| 5002Z | | | AK | | 0-0 | 77-11-11 | D40020J | S/R | | | D41788P | 22 | | | ALL |
| YAAA | | | | | 0-0 | 77-11-11 | GD02410 | ST.. | E | | D40020J | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4230

Page 21 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4300 | 286N4300 | | | E5-1 TO L. W/B DISC - L. ENG/GEN CONTROL | | | | | | | | | | | |
| 0001 | 20 | | GA | | 67-0 | 24-11-11 | D41898P | 27 | | | D40288J | 8 | | | 001-099 |
| 0001 | 20 | | GA | | 66-0 | 24-11-11 | D41898P | 27 | | | D40288J | 8 | | | 115-199 |
| 0002 | 16 | | GA | | 67-0 | 24-11-11 | D41898P | 8 | | | D40288J | 4 | 16 | | 001-099 |
| 0002 | 16 | | GA | | 66-0 | 24-11-11 | D41898P | 8 | | | D40288J | 4 | 16 | | 115-199 |
| 0602 | 20 | | GA | | 67-0 | SPARE | D40288J | 32 | | | D41898P | 16 | | | 001-099 |
| 0602 | 20 | | GA | | 66-0 | SPARE | D40288J | 32 | | | D41898P | 16 | | | 115-199 |
| 0603 | 20 | | GA | | 67-0 | SPARE | D40288J | 38 | | | D41898P | 17 | | | 001-099 |
| 0603 | 20 | | GA | | 66-0 | SPARE | D40288J | 38 | | | D41898P | 17 | | | 115-199 |
| 2001B | 20 | | GB | AD | 67-0 | 24-11-11 | D41898P | 19 | | | D40288J | 19 | | | 001-099 |
| 2001B | 20 | | GB | AD | 66-0 | 24-11-11 | D41898P | 19 | | | D40288J | 19 | | | 115-199 |
| 2001R | 20 | | GB | AD | 0-0 | 24-11-11 | D41898P | 18 | | | D40288J | 18 | | | ALL |
| 2002B | 20 | | GB | AE | 67-0 | 24-11-11 | D41898P | 7 | | | D40288J | 7 | | | 001-099 |
| 2002B | 20 | | GB | AE | 66-0 | 24-11-11 | D41898P | 7 | | | D40288J | 7 | | | 115-199 |
| 2002R | 20 | | GB | AE | 0-0 | 24-11-11 | D41898P | 15 | | | D40288J | 6 | | | ALL |
| 2003B | 20 | | GB | AG | 66-0 | SPARE | D41898P | 21 | | | D40288J | 21 | | | ALL |
| 2003R | 20 | | GB | AG | 0-0 | SPARE | D41898P | 26 | | | D40288J | 26 | | | ALL |
| 2501B | 20 | | GU | AB | 67-0 | 24-21-11 | D41898P | 10 | | | D40288J | 10 | | | 001-099 |
| 2501B | 20 | | GU | AB | 66-0 | 24-21-11 | D41898P | 10 | | | D40288J | 10 | | | 115-199 |
| 2501R | 20 | | GU | AB | 0-0 | 24-21-11 | D41898P | 9 | | | D40288J | 9 | | | ALL |
| 2501Z | | | | AB | 0-0 | 24-21-11 | D41898P | 11 | | | D40288J | 11 | | | ALL |
| 2502B | 20 | | GU | AF | 67-0 | 24-11-11 | D41898P | 22 | | | D40288J | 2 | | | 001-099 |
| 2502B | 20 | | GU | AF | 66-0 | 24-11-11 | D41898P | 22 | | | D40288J | 2 | | | 115-199 |
| 2502R | 20 | | GU | AF | 0-0 | 24-11-11 | D41898P | 20 | | | D40288J | 1 | | | ALL |
| 2502Z | | | | AF | 0-0 | 24-11-11 | D41898P | 5 | | | D40288J | 5 | | | ALL |
| 3001B | 18 | | GC | AA | 67-0 | 24-21-11 | D41898P | 1 | | | D40288J | 16 | 18 | | 001-099 |
| 3001B | 18 | | GC | AA | 66-0 | 24-21-11 | D41898P | 1 | | | D40288J | 16 | 18 | | 115-199 |
| 3001R | 18 | | GC | AA | 0-0 | 24-21-11 | D41898P | 4 | | | D40288J | 15 | 18 | | ALL |
| 3001Y | 18 | | GC | AA | 0-0 | 24-21-11 | D41898P | 2 | | | D40288J | 17 | 18 | | ALL |
| 4001B | 24 | | GN | AC | 67-0 | 24-21-11 | D41898P | 13 | | | D40288J | 13 | | | 001-099 |
| 4001B | 24 | | GN | AC | 66-0 | 24-21-11 | D41898P | 13 | | | D40288J | 13 | | | 115-199 |
| 4001G | 24 | | GN | AC | 0-0 | 24-21-11 | D41898P | 3 | | | D40288J | 3 | | | ALL |
| 4001R | 24 | | GN | AC | 0-0 | 24-21-11 | D41898P | 12 | | | D40288J | 12 | | | ALL |
| 4001Y | 24 | | GN | AC | 0-0 | 24-21-11 | D41898P | 14 | | | D40288J | 14 | | | ALL |
| YAAA | | | | | 0-0 | 24-11-11 | GD03212 | ST.. | E | | D40288J | S/R | | | ALL |
| W4302 | 286N4302 | | | E5-2 TO R. W/B DISC - R. ENG/GEN CONTROL | | | | | | | | | | | |
| 0001 | 20 | | GA | | 42-0 | 24-11-21 | D40398P | 8 | | | D40290J | 8 | | | ALL |
| 0002 | 16 | | GA | | 42-0 | 24-11-21 | D40398P | 16 | | | D40290J | 4 | | | ALL |
| 0004 | 20 | | GA | | 42-0 | SPARE | D40398P | 24 | | | D40290J | 29 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4300

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4302 | 286N4302 | | | E5-2 TO R. W/B DISC - R. ENG/GEN CONTROL (continued) | | | | | | | | | | | |
| 0005 | 20 | | GA | | 42-0 | SPARE | D40398P | 25 | | | D40290J | 30 | | | ALL |
| 2001B | 20 | | GB | AD | 42-0 | 24-11-21 | D40398P | 10 | | | D40290J | 18 | | | ALL |
| 2001R | 20 | | GB | AD | 0-0 | 24-11-21 | D40398P | 19 | | | D40290J | 19 | | | ALL |
| 2002B | 20 | | GB | AE | 42-0 | 24-11-21 | D40398P | 21 | | | D40290J | 6 | | | ALL |
| 2002R | 20 | | GB | AE | 0-0 | 24-11-21 | D40398P | 11 | | | D40290J | 7 | | | ALL |
| 2003B | 20 | | GB | AG | 42-0 | SPARE | D40398P | 7 | | | D40290J | 21 | | | ALL |
| 2003R | 20 | | GB | AG | 0-0 | SPARE | D40398P | 13 | | | D40290J | 23 | | | ALL |
| 2501B | 20 | | GU | AB | 42-0 | 24-21-21 | D40398P | 6 | | | D40290J | 10 | | | ALL |
| 2501R | 20 | | GU | AB | 0-0 | 24-21-21 | D40398P | 12 | | | D40290J | 9 | | | ALL |
| 2501Z | | | | AB | 0-0 | 24-21-21 | D40398P | 23 | | | D40290J | 11 | | | ALL |
| 2502B | 20 | | GU | AF | 42-0 | 24-11-21 | D40398P | 9 | | | D40290J | 1 | | | ALL |
| 2502R | 20 | | GU | AF | 0-0 | 24-11-21 | D40398P | 2 | | | D40290J | 2 | | | ALL |
| 2502Z | | | | AF | 0-0 | 24-11-21 | D40398P | 17 | | | D40290J | 5 | | | ALL |
| 3001B | 18 | | GC | AA | 42-0 | 24-21-21 | D40398P | 18 | | | D40290J | 16 | | | ALL |
| 3001R | 18 | | GC | AA | 0-0 | 24-21-21 | D40398P | 20 | | | D40290J | 15 | | | ALL |
| 3001Y | 18 | | GC | AA | 0-0 | 24-21-21 | D40398P | 22 | | | D40290J | 17 | | | ALL |
| 4001B | 24 | | GN | AC | 42-0 | 24-21-21 | D40398P | 1 | | | D40290J | 13 | | | ALL |
| 4001G | 24 | | GN | AC | 0-0 | 24-21-21 | D40398P | 3 | | | D40290J | 3 | | | ALL |
| 4001R | 24 | | GN | AC | 0-0 | 24-21-21 | D40398P | 4 | | | D40290J | 12 | | | ALL |
| 4001Y | 24 | | GN | AC | 0-0 | 24-21-21 | D40398P | 5 | | | D40290J | 14 | | | ALL |
| YAAA | | | | | 0-0 | 24-11-21 | GD00062 | ST.. | E | | D40290J | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4300

Page 2 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-----------------|----|----|-----|-------------|--|---------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4310 | 286N4310 | | | | | JUMPER BUNDLE, FORWARD SMOKE DETECTOR 1 | | | | | | | | | |
| 0001 | 20 | | GA | | 2-0 | 26-16-11 | D41264P | | | | D04402 | 4 | | | 001-099 |
| 0002 | 20 | | GA | | 2-0 | 26-16-11 | D41264P | | | | D04402 | 12 | | | 001-099 |
| 0003 | 20 | | GA | | 2-0 | 26-16-11 | D41264P | | | | D04402 | 11 | | | 001-099 |
| 0004 | 20 | | GA | | 2-0 | 26-16-11 | D41264P | | | | D04402 | 5 | | | 001-099 |
| 0005 | 20 | | GA | | 2-0 | 26-16-11 | D41264P | | | | D04402 | 9 | | | 001-099 |
| W4312 | 286N4312 | | | | | JUMPER BUNDLE, FWD BLOWER 1 | | | | | | | | | |
| 0423 | 20 | | GA | | 1-2 | 26-16-21 | D41256P | | | | D04424 | 2 | | | 001-099 |
| 0424 | 20 | | GA | | 1-2 | 26-16-21 | D41256P | | | | D04424 | 3 | | | 001-099 |
| 0425 | 22 | | GA | | 1-2 | 26-16-21 | D41256P | | | | D04424 | 1 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4310

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------|--------------------------------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4406 | 286N4406 | | | | P34, P31,P32 AC TIE BUS | | | | | | | | | | |
| 0001 | 04 | | CQ | | 7-10 | 24-21-51 | C00905 | T3 | H | * | C00904 | L1 | H | * | 001-099 |
| 0001 | 04 | | CQ | | 7-4 | 24-21-51 | C00905 | T3 | H | | C00904 | L1 | H | * | 115-199 |
| 0002 | 04 | | CQ | | 1-5 | 24-21-51 | C00905 | T3 | H | * | K00114 | A2 | H | * | 001-099 |
| 0002 | 04 | | CQ | | 1-5 | 24-21-51 | C00905 | T3 | H | | K00114 | A2 | H | * | 115-199 |
| 0003 | 04 | | CQ | | 5-11 | 24-21-51 | K00114 | A2 | H | * | C00902 | L1 | H | * | 001-099 |
| 0003 | 04 | | CQ | | 5-6 | 24-21-51 | K00114 | A2 | H | * | C00902 | L1 | H | * | 115-199 |
| 0004 | 04 | | CQ | | 5-5 | 24-21-51 | C00902 | L1 | H | * | C00904 | L1 | H | * | 001-099 |
| 0004 | 04 | | CQ | | 5-3 | 24-21-51 | C00902 | L1 | H | * | C00904 | L1 | H | * | 115-199 |
| 0005 | 04 | | CQ | | 7-10 | 24-21-51 | C00905 | T2 | H | * | C00904 | L2 | H | * | 001-099 |
| 0005 | 04 | | CQ | | 7-6 | 24-21-51 | C00905 | T2 | H | | C00904 | L2 | H | * | 115-199 |
| 0006 | 04 | | CQ | | 1-6 | 24-21-51 | C00905 | T2 | H | * | K00114 | B2 | H | * | 001-099 |
| 0006 | 04 | | CQ | | 1-6 | 24-21-51 | C00905 | T2 | H | | K00114 | B2 | H | * | 115-199 |
| 0007 | 04 | | CQ | | 6-1 | 24-21-51 | K00114 | B2 | H | * | C00902 | L2 | H | * | 001-099 |
| 0007 | 04 | | CQ | | 5-8 | 24-21-51 | K00114 | B2 | H | * | C00902 | L2 | H | * | 115-199 |
| 0008 | 04 | | CQ | | 5-3 | 24-21-51 | C00902 | L2 | H | * | C00904 | L2 | H | * | 001-099 |
| 0008 | 04 | | CQ | | 4-11 | 24-21-51 | C00902 | L2 | H | * | C00904 | L2 | H | * | 115-199 |
| 0009 | 04 | | CQ | | 8-3 | 24-21-51 | C00905 | T1 | H | * | C00904 | L3 | H | * | 001-099 |
| 0009 | 04 | | CQ | | 7-7 | 24-21-51 | C00905 | T1 | H | | C00904 | L3 | H | * | 115-199 |
| 0010 | 04 | | CQ | | 1-9 | 24-21-51 | C00905 | T1 | H | * | K00114 | C2 | H | * | 001-099 |
| 0010 | 04 | | CQ | | 1-8 | 24-21-51 | C00905 | T1 | H | | K00114 | C2 | H | * | 115-199 |
| 0011 | 04 | | CQ | | 6-8 | 24-21-51 | K00114 | C2 | H | * | C00902 | L3 | H | * | 001-099 |
| 0011 | 04 | | CQ | | 5-11 | 24-21-51 | K00114 | C2 | H | * | C00902 | L3 | H | * | 115-199 |
| 0012 | 04 | | CQ | | 4-10 | 24-21-51 | C00902 | L3 | H | * | C00904 | L3 | H | * | 001-099 |
| 0012 | 04 | | CQ | | 4-6 | 24-21-51 | C00902 | L3 | H | * | C00904 | L3 | H | * | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4400

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4420 | 286N4420 | | | P36 TO P37 - SEP 'L2' | | | | | | | | | | | |
| 0001 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 1 | D41030P | | | 1 | ALL |
| 0002 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 2 | D41030P | | | 2 | 115-199 |
| 0003 | 24 | | GK | | 11-0 | 30-31-11 | D41020P | | | 3 | D41030P | | | 3 | ALL |
| 0004 | 24 | | GK | | 11-0 | 30-31-11 | D41020P | | | 4 | D41030P | | | 4 | ALL |
| 0005 | 20 | | GA | | 11-0 | 27-62-11 | D41020P | | | 5 | D41030P | | | 5 | ALL |
| 0006 | 24 | | GK | | 11-0 | SPARE | D41020P | | | 6 | D41030P | | | 6 | ALL |
| 0007 | 24 | | GK | | 11-0 | 21-25-11 | D41020P | | | 7 | D41030P | | | 7 | ALL |
| 0008 | 24 | | GK | | 11-0 | 21-25-11 | D41020P | | | 8 | D41030P | | | 8 | ALL |
| 0009 | 24 | | GK | | 11-0 | 21-25-11 | D41020P | | | 9 | D41030P | | | 9 | ALL |
| 0010 | 24 | | GK | | 11-0 | 30-31-11 | D41020P | | | 10 | D41030P | | | 10 | ALL |
| 0011 | 24 | | GK | | 11-0 | 23-31-13 | D41020P | | | 11 | D41030P | | | 11 | ALL |
| 0012 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 12 | D41030P | | | 12 | 115-199 |
| 0013 | 20 | | GA | | 11-0 | 27-62-11 | D41020P | | | 13 | D41030P | | | 13 | 115-199 |
| 0014 | 20 | | GA | | 11-0 | SPARE | D41020P | | | 14 | D41030P | | | 14 | 001-099 |
| 0014 | 20 | | GA | | 11-0 | 27-62-11 | D41020P | | | 14 | D41030P | | | 14 | 115-199 |
| 0015 | 20 | | GA | | 11-0 | 27-62-11 | D41020P | | | 15 | D41030P | | | 15 | ALL |
| 0016 | 20 | | GA | | 11-0 | 27-62-11 | D41020P | | | 16 | D41030P | | | 16 | ALL |
| 0017 | 20 | | GA | | 10-0 | 27-62-11 | D41020P | | | 17 | D41030P | | | 17 | ALL |
| 0018 | 20 | | GA | | 11-0 | SPARE | D41020P | | | 18 | D41030P | | | 18 | 115-199 |
| 0019 | 24 | | GK | | 11-0 | 30-31-11 | D41020P | | | 19 | D41030P | | | 19 | ALL |
| 0020 | 24 | | GK | | 11-0 | 30-31-11 | D41020P | | | 20 | D41030P | | | 20 | ALL |
| 0021 | 24 | | GK | | 11-0 | 21-25-11 | D41020P | | | 21 | D41030P | | | 21 | ALL |
| 0022 | 24 | | GK | | 11-0 | SPARE | D41020P | | | 22 | D41030P | | | 22 | 115-199 |
| 0023 | 20 | | GA | | 11-0 | SPARE | D41020P | | | 23 | D41030P | | | 23 | 115-199 |
| 0024 | 20 | | GA | | 11-0 | SPARE | D41020P | | | 24 | D41030P | | | 24 | 115-199 |
| 0025 | 20 | | GA | | 11-0 | SPARE | D41020P | | | 25 | D41030P | | | 25 | 115-199 |
| 0026 | 20 | | GA | | 11-0 | SPARE | D41020P | | | 26 | D41030P | | | 26 | 115-199 |
| 0027 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 27 | D41030P | | | 27 | ALL |
| 0028 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 28 | D41030P | | | 28 | ALL |
| 0029 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 29 | D41030P | | | 29 | 115-199 |
| 0030 | 24 | | GK | | 11-0 | SPARE | D41020P | | | 30 | D41030P | | | 30 | ALL |
| 0031 | 22 | | GA | | 11-0 | 29-11-22 | D41020P | | | 31 | D41030P | | | 31 | ALL |
| 0032 | 22 | | GA | | 11-0 | 29-11-22 | D41020P | | | 32 | D41030P | | | 32 | ALL |
| 0033 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 33 | D41030P | | | 33 | 115-199 |
| 0034 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 34 | D41030P | | | 34 | 115-199 |
| 0035 | 24 | | GK | | 11-0 | SPARE | D41020P | | | 35 | D41030P | | | 35 | 115-199 |
| 0036 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 36 | D41030P | | | 36 | 115-199 |
| 0037 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 37 | D41030P | | | 37 | 115-199 |
| 0038 | 22 | | GA | | 11-0 | SPARE | D41020P | | | 38 | D41030P | | | 38 | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4420

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4420 | 286N4420 | P36 TO P37 - SEP 'L2' (continued) | | | | | | | | | | | | | |
| 0039 | 22 | GA | | | 11-0 | SPARE | D41020P | 39 | | | D41030P | 39 | | | 115-199 |
| 0040 | 24 | GK | | | 11-0 | SPARE | D41020P | 40 | | | D41030P | 40 | | | ALL |
| 0041 | 24 | GK | | | 11-0 | 21-25-11 | D41020P | 41 | | | D41030P | 41 | | | ALL |
| 0042 | 24 | GK | | | 11-0 | SPARE | D41020P | 42 | | | D41030P | 42 | | | 115-199 |
| 0043 | 24 | GK | | | 11-0 | 21-25-11 | D41020P | 43 | | | D41030P | 43 | | | ALL |
| 0044 | 22 | GA | | | 11-0 | SPARE | D41020P | 44 | | | D41030P | 44 | | | 115-199 |
| 0045 | 22 | GA | | | 11-0 | SPARE | D41020P | 45 | | | D41030P | 45 | | | 115-199 |
| 0046 | 22 | GA | | | 11-0 | SPARE | D41020P | 46 | | | D41030P | 46 | | | ALL |
| 0047 | 24 | GK | | | 11-0 | SPARE | D41020P | 47 | | | D41030P | 47 | | | 001-099 |
| 0047 | 22 | GA | | | 11-0 | 21-58-24 | D41020P | 47 | | | D41030P | 47 | | | 115-199 |
| 0048 | 24 | GK | | | 11-0 | SPARE | D41020P | 48 | | | D41030P | 48 | | | 001-099 |
| 0048 | 24 | GK | | | 11-0 | 21-58-24 | D41020P | 48 | | | D41030P | 48 | | | 115-199 |
| 0049 | 24 | GK | | | 11-0 | SPARE | D41020P | 49 | | | D41030P | 49 | | | 115-199 |
| 0050 | 24 | GK | | | 11-0 | 29-33-11 | D41020P | 50 | | | D41030P | 50 | | | ALL |
| 0051 | 20 | GA | | | 11-0 | 21-58-21 | D41020P | 51 | | | D41030P | 51 | | | ALL |
| 0052 | 20 | GA | | | 11-0 | 21-58-21 | D41020P | 52 | | | D41030P | 52 | | | ALL |
| 0053 | 20 | GA | | | 11-0 | SPARE | D41020P | 53 | | | D41030P | 53 | | | 115-199 |
| 0054 | 20 | GA | | | 11-0 | SPARE | D41020P | 54 | | | D41030P | | CAP | Y | 115-199 |
| 0055 | 20 | GA | | | 11-0 | SPARE | D41020P | 55 | | | D41030P | | CAP | Y | 115-199 |
| 0061 | 22 | GA | | | 20-0 | 32-61-11 | D41030P | 54 | | | SP01950 | 9 | | | 001-002, 115-199 |
| 0062 | 22 | GA | | | 20-0 | 32-61-11 | D41030P | 55 | | | SP01952 | 9 | | | 001-002, 115-199 |
| W4421 | 286N4421 | E4-1 TO E3-1 WIRE BUNDLE CHANNEL "L" | | | | | | | | | | | | | |
| 0001 | 22 | GA | | | 7-0 | SPARE | D41773P | 1 | | | D41775P | 1 | | | ALL |
| 0002 | 22 | GA | | | 7-0 | 27-41-11 | D41773P | 2 | | | D41775P | 2 | | | ALL |
| 0003 | 22 | GA | | | 7-0 | 22-24-21 | D41773P | 3 | | | D41775P | 3 | | | ALL |
| 0004 | 22 | GA | | | 7-0 | 22-24-21 | D41773P | 4 | | | D41775P | 4 | | | ALL |
| 0005 | 22 | GA | | | 7-0 | 22-24-21 | D41773P | 5 | | | D41775P | 5 | | | ALL |
| 0006 | 22 | GA | | | 7-0 | 27-41-31 | D41773P | 6 | | | D41775P | 6 | | | ALL |
| 0007 | 22 | GA | | | 7-0 | SPARE | D41773P | 7 | | | D41775P | 7 | | | ALL |
| 0008 | 22 | GA | | | 7-0 | 22-22-11 | D41773P | 8 | | | D41775P | 8 | | | ALL |
| 0009Y | 22 | QB | | | 7-0 | 27-41-11 | D41773P | 9 | | | D41775P | 9 | | | ALL |
| 0010Y | 22 | QB | | | 7-0 | 27-41-11 | D41773P | 10 | | | D41775P | 10 | | | ALL |
| 0011 | 22 | GA | | | 7-0 | 27-41-11 | D41773P | 11 | | | D41775P | 11 | | | ALL |
| 0012 | 22 | GA | | | 7-0 | 27-09-12 | D41773P | 12 | | | D41775P | 12 | | | ALL |
| 0013 | 22 | GA | | | 7-0 | 27-09-13 | D41773P | 13 | | | D41775P | 13 | | | ALL |
| 0014 | 22 | GA | | | 7-0 | 27-09-13 | D41773P | 14 | | | D41775P | 14 | | | ALL |
| 0015 | 22 | GA | | | 7-0 | 27-21-22 | D41773P | 15 | | | D41775P | 15 | | | ALL |
| 0016 | 22 | GA | | | 7-0 | 27-21-22 | D41773P | 16 | | | D41775P | 16 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4420

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4421 | 286N4421 | | | E4-1 TO E3-1 WIRE BUNDLE CHANNEL "L" (continued) | | | | | | | | | | | |
| 0017 | 22 | | GA | | 7-0 | 27-21-22 | D41773P | | 17 | | D41775P | | 17 | | ALL |
| 0018 | 22 | | GA | | 7-0 | 27-21-22 | D41773P | | 18 | | D41775P | | 18 | | ALL |
| 0021 | 20 | | GA | | 7-0 | 27-31-12 | D41773P | | 21 | | D41775P | | 21 | | ALL |
| 0022 | 20 | | GA | | 7-0 | 27-31-12 | D41773P | | 22 | | D41775P | | 22 | | ALL |
| 0031 | 20 | | GA | | 7-0 | 27-31-12 | D41773P | | 31 | | D41775P | | 31 | | ALL |
| 0032 | 22 | | GA | | 7-0 | 22-21-21 | D41773P | | 32 | | D41775P | | 32 | | ALL |
| 0036 | 22 | | GA | | 7-0 | 27-31-22 | D41773P | | 36 | | D41775P | | 36 | | ALL |
| 0037 | 22 | | GA | | 7-0 | 27-31-22 | D41773P | | 37 | | D41775P | | 37 | | ALL |
| 0038 | 22 | | GA | | 7-0 | 27-21-12 | D41773P | | 38 | | D41775P | | 38 | | ALL |
| 0039 | 22 | | GA | | 7-0 | SPARE | D41773P | | 39 | | D41775P | | 39 | | ALL |
| 0040 | 22 | | GA | | 7-0 | SPARE | D41773P | | 40 | | D41775P | | 40 | | 115-199 |
| 0041 | 22 | | GA | | 7-0 | SPARE | D41773P | | 41 | | D41775P | | 41 | | 115-199 |
| 2001B | 22 | | GB | AA | 7-0 | 27-21-22 | D41773P | | 24 | | D41775P | | 24 | | ALL |
| 2001R | 22 | | GB | AA | 0-0 | 27-21-22 | D41773P | | 23 | | D41775P | | 23 | | ALL |
| 2002B | 22 | | GB | AD | 7-0 | SPARE | D41773P | | 20 | | D41775P | | 20 | | 115-199 |
| 2002R | 22 | | GB | AD | 0-0 | SPARE | D41773P | | 19 | | D41775P | | 19 | | 115-199 |
| 3001B | 22 | | GC | AC | 7-0 | SPARE | D41773P | | 29 | | D41775P | | 29 | | 115-199 |
| 3001R | 22 | | GC | AC | 0-0 | SPARE | D41773P | | 28 | | D41775P | | 28 | | 115-199 |
| 3001Y | 22 | | GC | AC | 0-0 | SPARE | D41773P | | 30 | | D41775P | | 30 | | 115-199 |
| W4422 | 286N4422 | | | P36 TO P37 -SEP 'R2' | | | | | | | | | | | |
| 0001 | 24 | | GK | | 9-0 | SPARE | D41022P | | 1 | | D41032P | | 1 | | 115-199 |
| 0002 | 24 | | GK | | 10-0 | SPARE | D41022P | | 2 | | D41032P | | 2 | | 001-099 |
| 0002 | 22 | | GA | | 9-0 | 21-58-24 | D41022P | | 2 | | D41032P | | 2 | | 115-199 |
| 0003 | 24 | | GK | | 10-0 | SPARE | D41022P | | 3 | | D41032P | | 3 | | 001-099 |
| 0003 | 24 | | GK | | 9-0 | SPARE | D41022P | | 3 | | D41032P | | 3 | | 115-199 |
| 0004 | 24 | | GK | | 10-0 | 21-58-21 | D41022P | | 4 | | D41032P | | 4 | | 001-099 |
| 0004 | 24 | | GK | | 9-0 | 21-58-21 | D41022P | | 4 | | D41032P | | 4 | | 115-199 |
| 0005 | 20 | | GK | | 10-0 | 38-13-11 | D41032P | | 5 | | D41022P | | 5 | | 001-099 |
| 0005 | 24 | | GK | | 9-0 | SPARE | D41022P | | 5 | | D41032P | | 5 | | 115-199 |
| 0006 | 24 | | GK | | 9-0 | SPARE | D41022P | | 6 | | D41032P | | 6 | | 115-199 |
| 0007 | 22 | | GA | | 10-0 | 27-62-11 | D41022P | | 7 | | D41032P | | 7 | | 001-099 |
| 0007 | 20 | | GA | | 9-0 | 27-62-11 | D41022P | | 7 | | D41032P | | 7 | | 115-199 |
| 0008 | 20 | | GA | | 10-0 | 27-62-11 | D41022P | | 8 | | D41032P | | 8 | | 001-099 |
| 0008 | 20 | | GA | | 9-0 | 27-62-11 | D41022P | | 8 | | D41032P | | 8 | | 115-199 |
| 0009 | 22 | | GA | | 10-0 | 36-11-11 | D41022P | | 9 | | D41032P | | 9 | | 001-099 |
| 0009 | 22 | | GA | | 9-0 | 36-11-11 | D41022P | | 9 | | D41032P | | 9 | | 115-199 |
| 0010 | 22 | | GA | | 10-0 | 32-61-11 | D41022P | | 10 | | D41032P | | 10 | | 001-002 |
| 0010 | 22 | | GA | | 10-0 | 34-61-21 | D41022P | | 10 | | D41032P | | 10 | | 003-099 |

WIRE LIST

D280N032

91-21-11

Section W4420

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|------|----------------------------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4422 | 286N4422 | | | | P36 TO P37 -SEP 'R2' (continued) | | | | | | | | | | |
| 0010 | 22 | | GA | 9-0 | 32-61-11 | D41022P | | 10 | | | D41032P | 10 | | | 115-199 |
| 0011 | 24 | | GK | 10-0 | 21-58-12 | D41022P | | 11 | | | D41032P | 11 | | | 001-099 |
| 0011 | 24 | | GK | 9-0 | 21-58-12 | D41022P | | 11 | | | D41032P | 11 | | | 115-199 |
| 0012 | 24 | | GK | 10-0 | 21-58-12 | D41022P | | 12 | | | D41032P | 12 | | | 001-099 |
| 0012 | 24 | | GK | 9-0 | 21-58-12 | D41022P | | 12 | | | D41032P | 12 | | | 115-199 |
| 0013 | 24 | | GK | 10-0 | 30-31-12 | D41022P | | 13 | | | D41032P | 13 | | | 001-099 |
| 0013 | 24 | | GK | 9-0 | 30-31-12 | D41022P | | 13 | | | D41032P | 13 | | | 115-199 |
| 0014 | 24 | | GK | 10-0 | 30-31-12 | D41022P | | 14 | | | D41032P | 14 | | | 001-099 |
| 0014 | 24 | | GK | 9-0 | 30-31-12 | D41022P | | 14 | | | D41032P | 14 | | | 115-199 |
| 0015 | 24 | | GK | 10-0 | 30-31-12 | D41022P | | 15 | | | D41032P | 15 | | | 001-099 |
| 0015 | 24 | | GK | 9-0 | 30-31-12 | D41022P | | 15 | | | D41032P | 15 | | | 115-199 |
| 0016 | 24 | | GK | 10-0 | 30-31-12 | D41022P | | 16 | | | D41032P | 16 | | | 001-099 |
| 0016 | 24 | | GK | 9-0 | 30-31-12 | D41022P | | 16 | | | D41032P | 16 | | | 115-199 |
| 0017 | 20 | | GA | 10-0 | 21-58-13 | D41022P | | 17 | | | D41032P | 17 | | | 001-099 |
| 0017 | 20 | | GA | 9-0 | 21-58-13 | D41022P | | 17 | | | D41032P | 17 | | | 115-199 |
| 0018 | 20 | | GA | 9-0 | SPARE | D41022P | | 18 | | | D41032P | 18 | | | 115-199 |
| 0019 | 20 | | GA | 10-0 | 21-58-13 | D41022P | | 19 | | | D41032P | 19 | | | 001-099 |
| 0019 | 20 | | GA | 9-0 | 21-58-13 | D41022P | | 19 | | | D41032P | 19 | | | 115-199 |
| 0020 | 20 | | GA | 10-0 | SPARE | D41022P | | 20 | | | D41032P | 20 | | | 001-099 |
| 0020 | 20 | | GA | 9-0 | SPARE | D41022P | | 20 | | | D41032P | 20 | | | 115-199 |
| 0021 | 22 | | GA | 9-0 | SPARE | D41022P | | 21 | | | D41032P | 21 | | | 115-199 |
| 0022 | 22 | | GA | 9-0 | SPARE | D41022P | | 22 | | | D41032P | 22 | | | 115-199 |
| 0023 | 24 | | GK | 10-0 | 30-33-11 | D41022P | | 23 | | | D41032P | 23 | | | 001-099 |
| 0023 | 24 | | GK | 9-0 | 30-33-11 | D41022P | | 23 | | | D41032P | 23 | | | 115-199 |
| 0024 | 24 | | GK | 10-0 | 30-33-11 | D41022P | | 24 | | | D41032P | 24 | | | 001-099 |
| 0024 | 24 | | GK | 9-0 | 30-33-11 | D41022P | | 24 | | | D41032P | 24 | | | 115-199 |
| 0025 | 22 | | GA | 9-0 | SPARE | D41022P | | 25 | | | D41032P | 25 | | | 115-199 |
| 0026 | 22 | | GA | 10-0 | 38-13-11 | D41022P | | 26 | | | D41032P | 26 | | | 001-099 |
| 0026 | 18 | | GA | 9-0 | 38-13-11 | D41022P | | 26 | 18 | | D41032P | 26 | 18 | | 115-199 |
| 0027 | 22 | | GA | 10-0 | 38-13-11 | D41022P | | 27 | | | D41032P | 27 | | | 001-099 |
| 0027 | 18 | | GA | 9-0 | 38-13-11 | D41022P | | 27 | 18 | | D41032P | 27 | 18 | | 115-199 |
| 0028 | 22 | | GA | 9-0 | SPARE | D41022P | | 28 | | | D41032P | 28 | | | 115-199 |
| 0029 | 24 | | GK | 10-0 | 30-31-12 | D41022P | | 29 | | | D41032P | 29 | | | 001-099 |
| 0029 | 24 | | GK | 9-0 | 30-31-12 | D41022P | | 29 | | | D41032P | 29 | | | 115-199 |
| 0030 | 24 | | GK | 9-0 | SPARE | D41022P | | 30 | | | D41032P | 30 | | | 115-199 |
| 0031 | 24 | | GK | 10-0 | 36-11-41 | D41022P | | 31 | | | D41032P | 31 | | | 001-099 |
| 0031 | 24 | | GK | 9-0 | 36-11-41 | D41022P | | 31 | | | D41032P | 31 | | | 115-199 |
| 0032 | 24 | | GK | 10-0 | 30-31-12 | D41022P | | 32 | | | D41032P | 32 | | | 001-099 |
| 0032 | 24 | | GK | 9-0 | 30-31-12 | D41022P | | 32 | | | D41032P | 32 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4420

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|---------|------|--------|-------|---------|------|--------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W4422 | 286N4422 | | | | P36 TO P37 -SEP 'R2' (continued) | | | | | | | | | | | |
| 0033 | 24 | | GK | | 10-0 | 36-11-41 | | D41022P | | 33 | | D41032P | | 33 | | 001-099 |
| 0033 | 24 | | GK | | 9-0 | 36-11-41 | | D41022P | | 33 | | D41032P | | 33 | | 115-199 |
| 0034 | 24 | | GK | | 10-0 | 24-22-22 | | D41022P | | 34 | | D41032P | | 34 | | 001-099 |
| 0034 | 24 | | GK | | 9-0 | 24-22-22 | | D41022P | | 34 | | D41032P | | 34 | | 115-199 |
| 0035 | 24 | | GK | | 10-0 | 30-31-12 | | D41022P | | 35 | | D41032P | | 35 | | 001-099 |
| 0035 | 24 | | GK | | 9-0 | 30-31-12 | | D41022P | | 35 | | D41032P | | 35 | | 115-199 |
| 0036 | 24 | | GK | | 9-0 | SPARE | | D41022P | | 36 | | D41032P | | 36 | | 115-199 |
| 0037 | 24 | | GK | | 10-0 | 29-33-11 | | D41022P | | 37 | | D41032P | | 37 | | 001-099 |
| 0037 | 24 | | GK | | 9-0 | 29-33-11 | | D41022P | | 37 | | D41032P | | 37 | | 115-199 |
| 0038 | 24 | | GK | | 9-0 | SPARE | | D41022P | | 38 | | D41032P | | 38 | | 115-199 |
| 0039 | 24 | | GK | | 9-0 | SPARE | | D41022P | | 39 | | D41032P | | 39 | | 115-199 |
| 0040 | 22 | | GA | | 9-0 | 36-11-11 | | D41022P | | 40 | | D41032P | | 40 | | ALL |
| 0041 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 41 | | D41032P | | 41 | | ALL |
| 0042 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 42 | | D41032P | | 42 | | 115-199 |
| 0043 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 43 | | D41032P | | 43 | | 115-199 |
| 0044 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 44 | | D41032P | | 44 | | 115-199 |
| 0045 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 45 | | D41032P | | 45 | | 115-199 |
| 0046 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 46 | | D41032P | | 46 | | 115-199 |
| 0047 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 47 | | D41032P | | 47 | | 115-199 |
| 0048 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 48 | | D41032P | | 48 | | 115-199 |
| 0049 | 22 | | GA | | 9-0 | SPARE | | D41022P | | 49 | | D41032P | | 49 | | 115-199 |
| 0050 | 24 | | GK | | 9-0 | SPARE | | D41022P | | 50 | | D41032P | | 50 | | 115-199 |
| 0051 | 20 | | GA | | 10-0 | 27-62-11 | | D41022P | | 51 | | D41032P | | 51 | | 001-099 |
| 0051 | 20 | | GA | | 9-0 | SPARE | | D41022P | | 51 | | D41032P | | 51 | | 115-199 |
| 0052 | 20 | | GA | | 10-0 | 27-62-11 | | D41022P | | 52 | | D41032P | | 52 | | 001-099 |
| 0052 | 20 | | GA | | 9-0 | SPARE | | D41022P | | 52 | | D41032P | | 52 | | 115-199 |
| 5001B | 22 | | GU | AA | 9-0 | SPARE | | D41022P | | 53 | | D41032P | | 53 | | 115-199 |
| 5001R | 22 | | GU | AA | 0-0 | SPARE | | D41022P | | 54 | | D41032P | | 54 | | 115-199 |
| 5001Z | | | | AA | 0-0 | SPARE | | D41022P | | 55 | | D41032P | | 55 | | 115-199 |
| W4423 | 286N4423 | | | | E4-1 TO E3-1 WIRE BUNDLE CHANNEL "R" | | | | | | | | | | | |
| 0001 | 22 | | GA | | 6-0 | 22-24-11 | | D41777P | | 1 | | D41779P | | 1 | | ALL |
| 0002Y | 22 | | QB | | 6-0 | 27-41-11 | | D41777P | | 2 | | D41779P | | 2 | | ALL |
| 0003Y | 22 | | QB | | 6-0 | 27-41-11 | | D41777P | | 3 | | D41779P | | 3 | | ALL |
| 0004 | 22 | | GA | | 6-0 | 27-41-11 | | D41777P | | 4 | | D41779P | | 4 | | ALL |
| 0005 | 22 | | GA | | 6-0 | SPARE | | D41777P | | 5 | | D41779P | | 5 | | ALL |
| 0006Y | 22 | | QB | | 6-0 | 27-41-11 | | D41777P | | 6 | | D41779P | | 6 | | ALL |
| 0007 | 22 | | GA | | 6-0 | 27-09-12 | | D41777P | | 7 | | D41779P | | 7 | | ALL |
| 0008 | 22 | | GA | | 6-0 | 27-09-13 | | D41777P | | 8 | | D41779P | | 8 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4420

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4423 | | 286N4423 | | | | E4-1 TO E3-1 WIRE BUNDLE CHANNEL "R" (continued) | | | | | | | | | |
| 0009 | 22 | GA | | | 6-0 | 27-09-13 | D41777P | | 9 | | D41779P | | 9 | | ALL |
| 0010 | 22 | GA | | | 6-0 | 27-21-12 | D41777P | | 10 | | D41779P | | 10 | | ALL |
| 0011 | 22 | GA | | | 6-0 | 27-21-12 | D41777P | | 11 | | D41779P | | 11 | | ALL |
| 0012 | 22 | GA | | | 6-0 | 27-21-12 | D41777P | | 12 | | D41779P | | 12 | | ALL |
| 0013 | 22 | GA | | | 6-0 | 27-21-12 | D41777P | | 13 | | D41779P | | 13 | | ALL |
| 0014 | 22 | GA | | | 6-0 | 27-21-12 | D41777P | | 14 | | D41779P | | 14 | | ALL |
| 0022 | 20 | GA | | | 6-0 | 27-61-12 | D41777P | | 22 | | D41779P | | 22 | | ALL |
| 0023 | 22 | GA | | | 6-0 | 22-24-21 | D41777P | | 23 | | D41779P | | 23 | | ALL |
| 0024 | 22 | GA | | | 6-0 | 22-21-21 | D41779P | | 24 | | D41777P | | 24 | | ALL |
| 0031 | 22 | GA | | | 6-0 | 22-21-11 | D41777P | | 31 | | D41779P | | 31 | | ALL |
| 0032 | 22 | GA | | | 6-0 | 22-21-11 | D41777P | | 32 | | D41779P | | 32 | | ALL |
| 0033 | 22 | GA | | | 6-0 | 22-22-11 | D41777P | | 33 | | D41779P | | 33 | | ALL |
| 0034 | 22 | GA | | | 6-0 | 22-24-21 | D41777P | | 34 | | D41779P | | 34 | | ALL |
| 0035 | 22 | GA | | | 6-0 | 27-31-22 | D41777P | | 35 | | D41779P | | 35 | | ALL |
| 0036 | 22 | GA | | | 6-0 | 27-31-22 | D41777P | | 36 | | D41779P | | 36 | | ALL |
| 0037 | 22 | GA | | | 6-0 | SPARE | D41777P | | 37 | | D41779P | | 37 | | ALL |
| 0038 | 22 | GA | | | 6-0 | SPARE | D41777P | | 38 | | D41779P | | 38 | | ALL |
| 0039 | 22 | GA | | | 6-0 | SPARE | D41777P | | 39 | | D41779P | | 39 | | 115-199 |
| 0040 | 22 | GA | | | 6-0 | SPARE | D41777P | | 40 | | D41779P | | 40 | | 115-199 |
| 0041 | 22 | GA | | | 6-0 | SPARE | D41777P | | 41 | | D41779P | | 41 | | 115-199 |
| 0042Y | 22 | QB | | | 6-0 | 27-41-11 | D41777P | | 25 | | D41779P | | 25 | | 001-099 |
| 0042Y | 22 | QB | | | 6-0 | 27-41-11 | D41777P | | 42 | | D41779P | | 42 | | 115-199 |
| 0043Y | 22 | QB | | | 6-0 | 27-41-11 | D41777P | | 26 | | D41779P | | 26 | | 001-099 |
| 0043Y | 22 | QB | | | 6-0 | 27-41-11 | D41777P | | 43 | | D41779P | | 43 | | 115-199 |
| 0044 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 17 | | D41779P | | 17 | | 001-099 |
| 0044 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 44 | | D41779P | | 44 | | 115-199 |
| 0045 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 18 | | D41779P | | 18 | | 001-099 |
| 0045 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 45 | | D41779P | | 45 | | 115-199 |
| 0046 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 19 | | D41779P | | 19 | | 001-099 |
| 0046 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 46 | | D41779P | | 46 | | 115-199 |
| 0047 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 20 | | D41779P | | 20 | | 001-099 |
| 0047 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 47 | | D41779P | | 47 | | 115-199 |
| 0048 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 21 | | D41779P | | 21 | | 001-099 |
| 0048 | 22 | GA | | | 6-0 | 27-09-14 | D41777P | | 48 | | D41779P | | 48 | | 115-199 |
| 2001B | 22 | GB | AA | | 6-0 | 27-21-12 | D41777P | | 16 | | D41779P | | 16 | | ALL |
| 2001R | 22 | GB | AA | | 0-0 | 27-21-12 | D41777P | | 15 | | D41779P | | 15 | | ALL |
| 2002B | 22 | GB | AB | | 6-0 | SPARE | D41777P | | 18 | | D41779P | | 18 | | 115-199 |
| 2002R | 22 | GB | AB | | 0-0 | SPARE | D41777P | | 17 | | D41779P | | 17 | | 115-199 |
| 3001B | 22 | GC | AD | | 6-0 | SPARE | D41777P | | 20 | | D41779P | | 20 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4420

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4423 | 286N4423 | | | | E4-1 TO E3-1 WIRE BUNDLE CHANNEL "R" (continued) | | | | | | | | | | |
| 3001R | 22 | GC | AD | | 0-0 | SPARE | D41777P | 19 | | | D41779P | 19 | | | 115-199 |
| 3001Y | 22 | GC | AD | | 0-0 | SPARE | D41777P | 21 | | | D41779P | 21 | | | 115-199 |
| W4424 | 286N4424 | | | | P36 TO P37 - SEP 'S2' | | | | | | | | | | |
| 0001 | 24 | GK | | | 13-0 | 21-58-12 | D41024P | 1 | | | D41034P | 1 | | | ALL |
| 0002 | 24 | GK | | | 13-0 | SPARE | D41024P | 2 | | | D41034P | 2 | | | 115-199 |
| 0003 | 24 | GK | | | 12-0 | 21-58-12 | D41024P | 3 | | | D41034P | 3 | | | 001-002 |
| 0003 | 24 | GK | | | 13-0 | 21-58-12 | D41024P | 3 | | | D41034P | 3 | | | 003-099, 115-199 |
| 0004 | 20 | GA | | | 13-0 | SPARE | D41024P | 4 | | | D41034P | 4 | | | ALL |
| 0005 | 24 | GK | | | 13-0 | SPARE | D41024P | 5 | | | D41034P | 5 | | | 115-199 |
| 0006 | 24 | GK | | | 13-0 | SPARE | D41024P | 6 | | | D41034P | 6 | | | 115-199 |
| 0007 | 20 | GA | | | 13-0 | SPARE | D41024P | 7 | | | D41034P | 7 | | | 115-199 |
| 0008 | 22 | GA | | | 13-0 | 21-58-15 | D41024P | 8 | | | D41034P | 8 | | | 115-199 |
| 0009 | 22 | GA | | | 13-0 | 24-25-11 | D41034P | 9 | | | D41024P | 9 | | | 001-099 |
| 0009 | 22 | GA | | | 13-0 | 24-25-11 | D41024P | 9 | | | D41034P | 9 | | | 115-199 |
| 0010 | 24 | GK | | | 13-0 | SPARE | D41024P | 10 | | | D41034P | 10 | | | 115-199 |
| 0011 | 20 | GA | | | 12-0 | 29-21-31 | D41034P | 11 | | | D41024P | 11 | | | 001-002 |
| 0011 | 20 | GA | | | 13-0 | 29-21-31 | D41034P | 11 | | | D41024P | 11 | | | 003-099 |
| 0011 | 20 | GA | | | 13-0 | 29-21-31 | D41024P | 11 | | | D41034P | 11 | | | 115-199 |
| 0012 | 20 | GA | | | 12-0 | 29-21-31 | D41034P | 12 | | | D41024P | 12 | | | 001-002 |
| 0012 | 20 | GA | | | 13-0 | 29-21-31 | D41034P | 12 | | | D41024P | 12 | | | 003-099 |
| 0012 | 20 | GA | | | 13-0 | 29-21-31 | D41024P | 12 | | | D41034P | 12 | | | 115-199 |
| 0013 | 22 | GA | | | 12-0 | 29-22-11 | D41024P | 13 | | | D41034P | 13 | | | 001-002 |
| 0013 | 22 | GA | | | 13-0 | 29-22-11 | D41024P | 13 | | | D41034P | 13 | | | 003-099 |
| 0014 | 22 | GA | | | 12-0 | 29-22-11 | D41024P | 14 | | | D41034P | 14 | | | 001-002 |
| 0014 | 22 | GA | | | 13-0 | 29-22-11 | D41024P | 14 | | | D41034P | 14 | | | 003-099 |
| 0015 | 22 | GA | | | 12-0 | SPARE | D41024P | 15 | | | D41034P | 15 | | | 001-002 |
| 0015 | 22 | GA | | | 13-0 | SPARE | D41024P | 15 | | | D41034P | 15 | | | 003-099 |
| 0016 | 22 | GA | | | 12-0 | SPARE | D41024P | 16 | | | D41034P | 16 | | | 001-002 |
| 0016 | 22 | GA | | | 13-0 | SPARE | D41024P | 16 | | | D41034P | 16 | | | 003-099 |
| 0017 | 22 | GA | | | 12-0 | 21-58-15 | D41024P | 17 | | | D41034P | 17 | | | 001-002 |
| 0017 | 22 | GA | | | 13-0 | 21-58-15 | D41024P | 17 | | | D41034P | 17 | | | 003-099 |
| 0018 | 24 | GK | | | 12-0 | SPARE | D41024P | 18 | | | D41034P | 18 | | | 001-002 |
| 0018 | 24 | GK | | | 13-0 | SPARE | D41024P | 18 | | | D41034P | 18 | | | 003-099 |
| 0019 | 22 | GA | | | 12-0 | SPARE | D41024P | 19 | | | D41034P | 19 | | | 001-002 |
| 0019 | 22 | GA | | | 13-0 | SPARE | D41024P | 19 | | | D41034P | 19 | | | 003-099 |
| 0020 | 22 | GA | | | 13-0 | SPARE | D41024P | 20 | | | D41034P | 20 | | | 001-099 |
| 0021 | 16 | GA | | | 13-0 | 35-21-12 | D41024P | 21 | | | D41034P | 21 | | | ALL |
| 0022 | 22 | GA | | | 13-0 | SPARE | D41034P | 22 | | | D41024P | 22 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4420

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|-------------|---------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice |
| W4424 | 286N4424 | | | | P36 TO P37 - SEP 'S2' (continued) | | | | | | | | | | |
| 0022 | 22 | | GA | | 13-0 | SPARE | D41024P | | 22 | | | D41034P | 22 | | 115-199 |
| 0023 | 16 | | GA | | 13-0 | 35-21-13 | D41024P | | 23 | | | D41034P | 23 | | ALL |
| 0024 | 22 | | GA | | 13-0 | SPARE | D41034P | | 24 | | | D41024P | 24 | | 001-099 |
| 0024 | 22 | | GA | | 13-0 | SPARE | D41024P | | 24 | | | D41034P | 24 | | 115-199 |
| 0025 | 22 | | GA | | 13-0 | SPARE | D41034P | | 25 | | | D41024P | 25 | | 001-099 |
| 0025 | 22 | | GA | | 13-0 | SPARE | D41024P | | 25 | | | D41034P | 25 | | 115-199 |
| 0030 | 24 | | GK | | 13-0 | SPARE | D41024P | | 30 | | | D41034P | 30 | | 001-099 |
| 0038 | 22 | | GA | | 13-0 | 32-61-11 | D41034P | | 26 | | | SP01950 | | 9 | 003-099 |
| 0039 | 22 | | GA | | 13-0 | 32-61-11 | D41034P | | 27 | | | SP01952 | | 9 | 003-099 |
| 0040 | 22 | | GA | | 13-0 | 32-61-11 | D41024P | | 31 | | | D41034P | 31 | | 003-099 |
| 0041 | 22 | | GA | | 13-0 | SPARE | D41024P | | 32 | | | D41034P | 32 | | 003-099 |
| 0042 | 22 | | GA | | 13-0 | SPARE | D41024P | | 33 | | | D41034P | 33 | | 003-099 |
| 0043 | 20 | | GA | | 13-0 | SPARE | D41024P | | 34 | | | D41034P | 34 | | 003-099 |
| 0044 | 20 | | GA | | 13-0 | SPARE | D41024P | | 35 | | | D41034P | 35 | | 003-099 |
| 0045 | 20 | | GA | | 13-0 | SPARE | D41024P | | 36 | | | D41034P | 36 | | 003-099 |
| W4425 | 286N4425 | | | | E4-1 TO E3-1 WIRE BUNDLE CHANNEL "C" | | | | | | | | | | |
| 0001 | 22 | | GA | | 8-0 | 22-24-21 | D41781P | | 1 | | | D41783P | 1 | | ALL |
| 0002 | 22 | | GA | | 8-0 | 22-22-11 | D41781P | | 2 | | | D41783P | 3 | | ALL |
| 0003 | 22 | | GA | | 8-0 | 22-22-11 | D41781P | | 3 | | | D41783P | 2 | | ALL |
| 0004 | 22 | | GA | | 8-0 | 22-22-11 | D41781P | | 4 | | | D41783P | 4 | | ALL |
| 0005 | 22 | | GA | | 8-0 | 27-09-13 | D41781P | | 5 | | | D41783P | 5 | | ALL |
| 0006 | 22 | | GA | | 8-0 | 27-09-13 | D41781P | | 6 | | | D41783P | 6 | | ALL |
| 0010 | 22 | | GA | | 8-0 | 27-09-12 | D41781P | | 10 | | | D41783P | 10 | | ALL |
| 0011 | 22 | | GA | | 8-0 | 22-21-21 | D41781P | | 11 | | | D41783P | 11 | | ALL |
| 0012 | 22 | | GA | | 8-0 | 27-09-12 | D41781P | | 12 | | | D41783P | 12 | | ALL |
| 0013 | 22 | | GA | | 8-0 | SPARE | D41781P | | 13 | | | D41783P | 13 | | ALL |
| 0014 | 22 | | GA | | 8-0 | SPARE | D41781P | | 14 | | | D41783P | 14 | | ALL |
| 0020 | 20 | | GA | | 8-0 | SPARE | D41781P | | 20 | | | D41783P | 20 | | 115-199 |
| 0024 | 22 | | GA | | 8-0 | SPARE | D41781P | | 24 | | | D41783P | 24 | | 115-199 |
| 2001B | 22 | | GB | AB | 8-0 | SPARE | D41781P | | 15 | | | D41783P | 15 | | 115-199 |
| 2001R | 22 | | GB | AB | 0-0 | SPARE | D41781P | | 16 | | | D41783P | 16 | | 115-199 |
| 2501B | 24 | | G2 | AA | 8-0 | 22-22-11 | D41781P | | 7 | | | D41783P | 7 | | ALL |
| 2501R | 24 | | G2 | AA | 0-0 | 22-22-11 | D41781P | | 8 | | | D41783P | 8 | | ALL |
| 2501Z | | | | AA | 0-0 | 22-22-11 | D41781P | | 9 | | | D41783P | 9 | | ALL |
| 3001B | 22 | | GC | AC | 8-0 | SPARE | D41781P | | 21 | | | D41783P | 21 | | 115-199 |
| 3001R | 22 | | GC | AC | 0-0 | SPARE | D41781P | | 22 | | | D41783P | 22 | | 115-199 |
| 3001Y | 22 | | GC | AC | 0-0 | SPARE | D41781P | | 23 | | | D41783P | 23 | | 115-199 |
| 5001B | 24 | | G2 | AD | 8-0 | 22-21-21 | D41781P | | 18 | | | D41783P | 18 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4420

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4425 | 286N4425 | | | | E4-1 TO E3-1 WIRE BUNDLE CHANNEL "C" (continued) | | | | | | | | | | | | |
| 5001R | 24 | G2 | | AD | 0-0 | 22-21-21 | D41781P | 17 | | | D41783P | 17 | | | ALL | | |
| 5001Z | | | | AD | 0-0 | 22-21-21 | D41781P | 19 | | | D41783P | 19 | | | ALL | | |
| W4427 | 286N4427 | | | | E4-1 TO E3-1 WIRE BUNDLE CHANNEL "S" | | | | | | | | | | | | |
| 0001 | 22 | GA | | | 5-0 | 22-24-21 | D41785P | 1 | | | D41787P | 1 | | | ALL | | |
| 0002 | 22 | GA | | | 5-0 | 22-22-11 | D41785P | 2 | | | D41787P | 2 | | | ALL | | |
| 0003 | 22 | GA | | | 5-0 | 27-41-11 | D41785P | 3 | | | D41787P | 3 | | | ALL | | |
| 0004 | 22 | GA | | | 5-0 | 27-41-11 | D41785P | 4 | | | D41787P | 4 | | | ALL | | |
| 0005 | 22 | GA | | | 5-0 | SPARE | D41785P | 5 | | | D41787P | 5 | | | ALL | | |
| 0006 | 22 | GA | | | 5-0 | 27-21-12 | D41785P | 6 | | | D41787P | 6 | | | ALL | | |
| 0007 | 22 | GA | | | 5-0 | 27-31-12 | D41785P | 7 | | | D41787P | 7 | | | ALL | | |
| 0008 | 22 | GA | | | 5-0 | 27-31-12 | D41785P | 8 | | | D41787P | 8 | | | ALL | | |
| 0009 | 22 | GA | | | 5-0 | 27-31-12 | D41785P | 9 | | | D41787P | 9 | | | ALL | | |
| 0010 | 22 | GA | | | 5-0 | 27-61-12 | D41785P | 10 | | | D41787P | 10 | | | ALL | | |
| 0011 | 22 | GA | | | 5-0 | 22-21-21 | D41785P | 11 | | | D41787P | 11 | | | ALL | | |
| 0012 | 22 | GA | | | 5-0 | 22-21-21 | D41785P | 12 | | | D41787P | 12 | | | ALL | | |
| 0013 | 22 | GA | | | 5-0 | 27-09-14 | D41785P | 13 | | | D41787P | 13 | | | ALL | | |
| 0014 | 22 | GA | | | 5-0 | SPARE | D41785P | 14 | | | D41787P | 14 | | | ALL | | |
| 0017 | 22 | GA | | | 5-0 | 27-09-14 | D41785P | 17 | | | D41787P | 17 | | | ALL | | |
| 0018 | 22 | GA | | | 5-0 | 27-09-14 | D41785P | 18 | | | D41787P | 18 | | | ALL | | |
| 0023 | 22 | GA | | | 5-0 | 27-09-14 | D41785P | 23 | | | D41787P | 23 | | | ALL | | |
| 0024 | 22 | GA | | | 5-0 | 27-09-14 | D41785P | 24 | | | D41787P | 24 | | | ALL | | |
| 2001B | 22 | GB | AA | | 5-0 | SPARE | D41785P | 15 | | | D41787P | 15 | | | ALL | | |
| 2001R | 22 | GB | AA | | 0-0 | SPARE | D41785P | 16 | | | D41787P | 16 | | | ALL | | |
| 2002B | 22 | GB | AB | | 5-0 | SPARE | D41785P | 19 | | | D41787P | 19 | | | ALL | | |
| 2002R | 22 | GB | AB | | 0-0 | SPARE | D41785P | 20 | | | D41787P | 20 | | | ALL | | |

WIRE LIST

D280N032

91-21-11
Section W4420
Page 9 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|----------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4441 | 286N4441 | | | CENTER EFIS-LEFT REDUNDANT | | | | | | | | | | | |
| 2501T | 24 | BV | AA | | 9-0 | 34-22-35 | D41085P | 1 | | | D41087P | 1 | | | ALL |
| 2501W | 24 | BV | AA | | 0-0 | 34-22-35 | D41085P | 2 | | | D41087P | 2 | | | ALL |
| 2501Z | | | AA | | 0-0 | 34-22-35 | D41085P | 3 | | | D41087P | 3 | | | ALL |
| 2502T | 24 | BV | AB | | 9-0 | 34-22-35 | D41085P | 4 | | | D41087P | 4 | | | ALL |
| 2502W | 24 | BV | AB | | 0-0 | 34-22-35 | D41085P | 5 | | | D41087P | 5 | | | ALL |
| 2502Z | | | AB | | 0-0 | 34-22-35 | D41085P | 6 | | | D41087P | 6 | | | ALL |
| 2503T | 24 | BV | AC | | 9-0 | 34-22-35 | D41085P | 7 | | | D41087P | 7 | | | ALL |
| 2503W | 24 | BV | AC | | 0-0 | 34-22-35 | D41085P | 8 | | | D41087P | 8 | | | ALL |
| 2503Z | | | AC | | 0-0 | 34-22-35 | D41085P | 9 | | | D41087P | 9 | | | ALL |
| 2504T | 24 | BV | AD | | 9-0 | 34-22-35 | D41085P | 10 | | | D41087P | 10 | | | ALL |
| 2504W | 24 | BV | AD | | 0-0 | 34-22-35 | D41085P | 11 | | | D41087P | 11 | | | ALL |
| 2504Z | | | AD | | 0-0 | 34-22-35 | D41085P | 12 | | | D41087P | 12 | | | ALL |
| 2505T | 24 | BV | AE | | 9-0 | 34-22-35 | D41085P | 13 | | | D41087P | 13 | | | ALL |
| 2505W | 24 | BV | AE | | 0-0 | 34-22-35 | D41085P | 14 | | | D41087P | 14 | | | ALL |
| 2505Z | | | AE | | 0-0 | 34-22-35 | D41085P | 15 | | | D41087P | 15 | | | ALL |
| 2506T | 24 | BV | AF | | 9-0 | 34-22-35 | D41085P | 16 | | | D41087P | 16 | | | ALL |
| 2506W | 24 | BV | AF | | 0-0 | 34-22-35 | D41085P | 17 | | | D41087P | 17 | | | ALL |
| 2506Z | | | AF | | 0-0 | 34-22-35 | D41085P | 18 | | | D41087P | 18 | | | ALL |
| 2507T | 24 | BV | AG | | 9-0 | 34-22-35 | D41085P | 19 | | | D41087P | 19 | | | ALL |
| 2507W | 24 | BV | AG | | 0-0 | 34-22-35 | D41085P | 20 | | | D41087P | 20 | | | ALL |
| 2507Z | | | AG | | 0-0 | 34-22-35 | D41085P | 21 | | | D41087P | 21 | | | ALL |
| 2508T | 24 | BV | AH | | 9-0 | 34-22-35 | D41085P | 22 | | | D41087P | 22 | | | ALL |
| 2508W | 24 | BV | AH | | 0-0 | 34-22-35 | D41085P | 23 | | | D41087P | 23 | | | ALL |
| 2508Z | | | AH | | 0-0 | 34-22-35 | D41085P | 24 | | | D41087P | 24 | | | ALL |
| 2509T | 24 | BV | AI | | 9-0 | 34-22-35 | D41085P | 25 | | | D41087P | 25 | | | ALL |
| 2509W | 24 | BV | AI | | 0-0 | 34-22-35 | D41085P | 26 | | | D41087P | 26 | | | ALL |
| 2509Z | | | AI | | 0-0 | 34-22-35 | D41085P | 27 | | | D41087P | 27 | | | ALL |
| 2510T | 24 | BV | AJ | | 9-0 | 34-22-35 | D41085P | 28 | | | D41087P | 28 | | | ALL |
| 2510W | 24 | BV | AJ | | 0-0 | 34-22-35 | D41085P | 29 | | | D41087P | 29 | | | ALL |
| 2510Z | | | AJ | | 0-0 | 34-22-35 | D41085P | 30 | | | D41087P | 30 | | | ALL |
| 2511T | 24 | BV | AK | | 9-0 | 34-22-35 | D41085P | 31 | | | D41087P | 31 | | | ALL |
| 2511W | 24 | BV | AK | | 0-0 | 34-22-35 | D41085P | 32 | | | D41087P | 32 | | | ALL |
| 2511Z | | | AK | | 0-0 | 34-22-35 | D41085P | 33 | | | D41087P | 33 | | | ALL |
| 2512T | 24 | BV | AL | | 9-0 | 34-22-35 | D41085P | 34 | | | D41087P | 34 | | | ALL |
| 2512W | 24 | BV | AL | | 0-0 | 34-22-35 | D41085P | 35 | | | D41087P | 35 | | | ALL |
| 2512Z | | | AL | | 0-0 | 34-22-35 | D41085P | 36 | | | D41087P | 36 | | | ALL |
| 2513T | 24 | BV | AM | | 9-0 | 34-22-35 | D41085P | 37 | | | D41087P | 37 | | | ALL |
| 2513W | 24 | BV | AM | | 0-0 | 34-22-35 | D41085P | 38 | | | D41087P | 38 | | | ALL |
| 2513Z | | | AM | | 0-0 | 34-22-35 | D41085P | 39 | | | D41087P | 39 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4440

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4441 | 286N4441 | | | | CENTER EFIS-LEFT REDUNDANT (continued) | | | | | | | | | | | |
| 2514T | 24 | | BV | AN | 9-0 | 34-22-35 | | D41085P | | | | D41087P | 40 | | | ALL |
| 2514W | 24 | | BV | AN | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 41 | | | ALL |
| 2514Z | | | | AN | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 42 | | | ALL |
| 2515T | 24 | | BV | AO | 9-0 | 34-22-35 | | D41085P | | | | D41087P | 43 | | | ALL |
| 2515W | 24 | | BV | AO | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 44 | | | ALL |
| 2515Z | | | | AO | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 45 | | | ALL |
| 2516T | 24 | | BV | AP | 9-0 | 34-22-35 | | D41085P | | | | D41087P | 46 | | | ALL |
| 2516W | 24 | | BV | AP | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 47 | | | ALL |
| 2516Z | | | | AP | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 48 | | | ALL |
| 2517T | 24 | | BV | AQ | 9-0 | 34-22-35 | | D41085P | | | | D41087P | 49 | | | ALL |
| 2517W | 24 | | BV | AQ | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 50 | | | ALL |
| 2517Z | | | | AQ | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 51 | | | ALL |
| 2518T | 24 | | BV | AR | 9-0 | 34-22-35 | | D41085P | | | | D41087P | 52 | | | ALL |
| 2518W | 24 | | BV | AR | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 53 | | | ALL |
| 2518Z | | | | AR | 0-0 | 34-22-35 | | D41085P | | | | D41087P | 54 | | | ALL |
| W4443 | 286N4443 | | | | CENTER EFIS-RIGHT REDUNDANT | | | | | | | | | | | |
| 2501T | 24 | | BV | AA | 8-0 | 34-22-34 | | D40881P | | | | D40883P | 1 | | | 001-099 |
| 2501T | 24 | | BV | AA | 7-0 | 34-22-34 | | D40881P | | | | D40883P | 1 | | | 115-199 |
| 2501W | 24 | | BV | AA | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 2 | | | ALL |
| 2501Z | | | | AA | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 3 | | | ALL |
| 2502T | 24 | | BV | AB | 8-0 | 34-22-34 | | D40881P | | | | D40883P | 4 | | | 001-099 |
| 2502T | 24 | | BV | AB | 7-0 | 34-22-34 | | D40881P | | | | D40883P | 4 | | | 115-199 |
| 2502W | 24 | | BV | AB | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 5 | | | ALL |
| 2502Z | | | | AB | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 6 | | | ALL |
| 2503T | 24 | | BV | AC | 8-0 | 34-22-34 | | D40881P | | | | D40883P | 7 | | | 001-099 |
| 2503T | 24 | | BV | AC | 7-0 | 34-22-34 | | D40881P | | | | D40883P | 7 | | | 115-199 |
| 2503W | 24 | | BV | AC | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 8 | | | ALL |
| 2503Z | | | | AC | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 9 | | | ALL |
| 2504T | 24 | | BV | AD | 8-0 | 34-22-34 | | D40881P | | | | D40883P | 10 | | | 001-099 |
| 2504T | 24 | | BV | AD | 7-0 | 34-22-34 | | D40881P | | | | D40883P | 10 | | | 115-199 |
| 2504W | 24 | | BV | AD | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 11 | | | ALL |
| 2504Z | | | | AD | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 12 | | | ALL |
| 2505T | 24 | | BV | AE | 8-0 | 34-22-34 | | D40881P | | | | D40883P | 13 | | | 001-099 |
| 2505T | 24 | | BV | AE | 7-0 | 34-22-34 | | D40881P | | | | D40883P | 13 | | | 115-199 |
| 2505W | 24 | | BV | AE | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 14 | | | ALL |
| 2505Z | | | | AE | 0-0 | 34-22-34 | | D40881P | | | | D40883P | 15 | | | ALL |
| 2506T | 24 | | BV | AF | 8-0 | 34-22-34 | | D40881P | | | | D40883P | 16 | | | 001-099 |
| 2506T | 24 | | BV | AF | 7-0 | 34-22-34 | | D40881P | | | | D40883P | 16 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4440

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|----------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4443 | 286N4443 | | | CENTER EFIS-RIGHT REDUNDANT (continued) | | | | | | | | | | | |
| 2506W | 24 | BV | AF | 0-0 | 34-22-34 | D40881P | | 17 | | | D40883P | 17 | | | ALL |
| 2506Z | | | AF | 0-0 | 34-22-34 | D40881P | | 18 | | | D40883P | 18 | | | ALL |
| 2507T | 24 | BV | AG | 8-0 | 34-22-34 | D40881P | | 19 | | | D40883P | 19 | | | 001-099 |
| 2507T | 24 | BV | AG | 7-0 | 34-22-34 | D40881P | | 19 | | | D40883P | 19 | | | 115-199 |
| 2507W | 24 | BV | AG | 0-0 | 34-22-34 | D40881P | | 20 | | | D40883P | 20 | | | ALL |
| 2507Z | | | AG | 0-0 | 34-22-34 | D40881P | | 21 | | | D40883P | 21 | | | ALL |
| 2508T | 24 | BV | AH | 8-0 | 34-22-34 | D40881P | | 22 | | | D40883P | 22 | | | 001-099 |
| 2508T | 24 | BV | AH | 7-0 | 34-22-34 | D40881P | | 22 | | | D40883P | 22 | | | 115-199 |
| 2508W | 24 | BV | AH | 0-0 | 34-22-34 | D40881P | | 23 | | | D40883P | 23 | | | ALL |
| 2508Z | | | AH | 0-0 | 34-22-34 | D40881P | | 24 | | | D40883P | 24 | | | ALL |
| 2509T | 24 | BV | AI | 8-0 | 34-22-34 | D40881P | | 25 | | | D40883P | 25 | | | 001-099 |
| 2509T | 24 | BV | AI | 7-0 | 34-22-34 | D40881P | | 25 | | | D40883P | 25 | | | 115-199 |
| 2509W | 24 | BV | AI | 0-0 | 34-22-34 | D40881P | | 26 | | | D40883P | 26 | | | ALL |
| 2509Z | | | AI | 0-0 | 34-22-34 | D40881P | | 27 | | | D40883P | 27 | | | ALL |
| 2510T | 24 | BV | AJ | 8-0 | 34-22-34 | D40881P | | 28 | | | D40883P | 28 | | | 001-099 |
| 2510T | 24 | BV | AJ | 7-0 | 34-22-34 | D40881P | | 28 | | | D40883P | 28 | | | 115-199 |
| 2510W | 24 | BV | AJ | 0-0 | 34-22-34 | D40881P | | 29 | | | D40883P | 29 | | | ALL |
| 2510Z | | | AJ | 0-0 | 34-22-34 | D40881P | | 30 | | | D40883P | 30 | | | ALL |
| 2511T | 24 | BV | AK | 8-0 | 34-22-34 | D40881P | | 31 | | | D40883P | 31 | | | 001-099 |
| 2511T | 24 | BV | AK | 7-0 | 34-22-34 | D40881P | | 31 | | | D40883P | 31 | | | 115-199 |
| 2511W | 24 | BV | AK | 0-0 | 34-22-34 | D40881P | | 32 | | | D40883P | 32 | | | ALL |
| 2511Z | | | AK | 0-0 | 34-22-34 | D40881P | | 33 | | | D40883P | 33 | | | ALL |
| 2512T | 24 | BV | AL | 8-0 | 34-22-34 | D40881P | | 34 | | | D40883P | 34 | | | 001-099 |
| 2512T | 24 | BV | AL | 7-0 | 34-22-34 | D40881P | | 34 | | | D40883P | 34 | | | 115-199 |
| 2512W | 24 | BV | AL | 0-0 | 34-22-34 | D40881P | | 35 | | | D40883P | 35 | | | ALL |
| 2512Z | | | AL | 0-0 | 34-22-34 | D40881P | | 36 | | | D40883P | 36 | | | ALL |
| 2513T | 24 | BV | AM | 8-0 | 34-22-34 | D40881P | | 37 | | | D40883P | 37 | | | 001-099 |
| 2513T | 24 | BV | AM | 7-0 | 34-22-34 | D40881P | | 37 | | | D40883P | 37 | | | 115-199 |
| 2513W | 24 | BV | AM | 0-0 | 34-22-34 | D40881P | | 38 | | | D40883P | 38 | | | ALL |
| 2513Z | | | AM | 0-0 | 34-22-34 | D40881P | | 39 | | | D40883P | 39 | | | ALL |
| 2514T | 24 | BV | AN | 8-0 | 34-22-34 | D40881P | | 40 | | | D40883P | 40 | | | 001-099 |
| 2514T | 24 | BV | AN | 7-0 | 34-22-34 | D40881P | | 40 | | | D40883P | 40 | | | 115-199 |
| 2514W | 24 | BV | AN | 0-0 | 34-22-34 | D40881P | | 41 | | | D40883P | 41 | | | ALL |
| 2514Z | | | AN | 0-0 | 34-22-34 | D40881P | | 42 | | | D40883P | 42 | | | ALL |
| 2515T | 24 | BV | AO | 8-0 | 34-22-34 | D40881P | | 43 | | | D40883P | 43 | | | 001-099 |
| 2515T | 24 | BV | AO | 7-0 | 34-22-34 | D40881P | | 43 | | | D40883P | 43 | | | 115-199 |
| 2515W | 24 | BV | AO | 0-0 | 34-22-34 | D40881P | | 44 | | | D40883P | 44 | | | ALL |
| 2515Z | | | AO | 0-0 | 34-22-34 | D40881P | | 45 | | | D40883P | 45 | | | ALL |
| 2516T | 24 | BV | AP | 8-0 | 34-22-34 | D40881P | | 46 | | | D40883P | 46 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4440

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4443 | 286N4443 | | | CENTER EFIS-RIGHT REDUNDANT (continued) | | | | | | | | | | | |
| 2516T | 24 | BV | AP | | 7-0 | 34-22-34 | D40881P | | | | D40883P | 46 | | | 115-199 |
| 2516W | 24 | BV | AP | | 0-0 | 34-22-34 | D40881P | | | | D40883P | 47 | | | ALL |
| 2516Z | | | AP | | 0-0 | 34-22-34 | D40881P | | | | D40883P | 48 | | | ALL |
| 2517T | 24 | BV | AQ | | 8-0 | 34-22-34 | D40881P | | | | D40883P | 49 | | | 001-099 |
| 2517T | 24 | BV | AQ | | 7-0 | 34-22-34 | D40881P | | | | D40883P | 49 | | | 115-199 |
| 2517W | 24 | BV | AQ | | 0-0 | 34-22-34 | D40881P | | | | D40883P | 50 | | | ALL |
| 2517Z | | | AQ | | 0-0 | 34-22-34 | D40881P | | | | D40883P | 51 | | | ALL |
| 2518T | 24 | BV | AR | | 8-0 | 34-22-34 | D40881P | | | | D40883P | 52 | | | 001-099 |
| 2518T | 24 | BV | AR | | 7-0 | 34-22-34 | D40881P | | | | D40883P | 52 | | | 115-199 |
| 2518W | 24 | BV | AR | | 0-0 | 34-22-34 | D40881P | | | | D40883P | 53 | | | ALL |
| 2518Z | | | AR | | 0-0 | 34-22-34 | D40881P | | | | D40883P | 54 | | | ALL |
| W4449 | 286N4449 | | | ATC COAX FROM TOP ANT RF SWITCH TO TOP ANT | | | | | | | | | | | |
| 001CO | | | AA | | 0-0 | 34-53-11 | D01443 | | = C1 | | D01431 | | = C1 | | ALL |
| 001CX | | JB | AA | | 18-6 | 34-53-11 | D01443 | | = A1 | | D01431 | | = A1 | | ALL |

WIRE LIST

D280N032

91-21-11
Section W4440
Page 4 End
Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-----|--|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4451 | 286N4451 | | | | ATC COAX FROM E3-3 TO TOP ANT RF SWITCH | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-53-11 | D01429 | = C1 | | | D41851P | = C1 | | | ALL |
| 001CX | | | JB | AA | 5-6 | 34-53-11 | D01429 | = A1 | | | D41851P | = A1 | | | ALL |
| W4453 | 286N4453 | | | | ATC COAX FROM E3-3 TO BOTTOM ANT RF SWITCH | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-53-11 | D01437 | = C1 | | | D41753P | = C1 | | | ALL |
| 001CX | | | JB | AA | 5-1 | 34-53-11 | D01437 | = A1 | | | D41753P | = A1 | | | 001-099 |
| 001CX | | | JB | AA | 5-6 | 34-53-11 | D01437 | = A1 | | | D41753P | = A1 | | | 115-199 |
| W4455 | 286N4455 | | | | ATC COAX FROM E3-2 TO TOP ANT RF SWITCH | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-53-21 | D01433 | = C1 | | | D41801P | = C1 | | | ALL |
| 001CX | | | JB | AA | 5-6 | 34-53-21 | D01433 | = A1 | | | D41801P | = A1 | | | ALL |
| W4457 | 286N4457 | | | | ATC COAX FROM E3-2 TO BOTTOM ANT RF SWITCH | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-53-21 | D01441 | = C1 | | | D41755P | = C1 | | | ALL |
| 001CX | | | JB | AA | 5-6 | 34-53-21 | D01441 | = A1 | | | D41755P | = A1 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4450

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | From | | | To | | | | Effectivity | | | |
|------------------------|-------------|----|----|-----------------------------|-------|----------|---------|-------|------|------|--------|-------------|-------|------|---------|
| | GA | CO | TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | | Equip | Term | Type |
| W4465 | 286N4465 | | | XPDR-R COAX, E3-2 TO ANT | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-53-11 | D00249 | = C1 | | | D01439 | = C1 | | | ALL |
| 001CX | | | JB | AA | 19-11 | 34-53-11 | D00249 | = A1 | | | D01439 | = A1 | | | ALL |
| W4467 | 286N4467 | | | XPDR/DME COAX, E3-3 TO E3-2 | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-53-11 | D01685 | = C1 | | | D02126 | = C1 | | | ALL |
| 001CX | | | BR | AA | 5-6 | 34-53-11 | D01685 | = A1 | | | D02126 | = A1 | | | 001-099 |
| 001CX | | | BR | AA | 8-0 | 34-53-11 | D01685 | = A1 | | | D02126 | = A1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4460

Page 1 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT | | | | | | | | | | | |
| 0001 | 24 | | GK | | 16-0 | 34-61-14 | D41473P | | 16 | | D41089P | | 16 | | ALL |
| 0002 | 24 | | GK | | 22-0 | 34-61-23 | D41089P | | 17 | | D41309P | | 17 | | ALL |
| 0003 | 24 | | GK | | 20-0 | 34-61-15 | D41317P | | 21 | | D41089P | | 21 | | ALL |
| 0004 | 24 | | GK | | 20-0 | 34-61-15 | D41317P | | 22 | | D41089P | | 22 | | ALL |
| 0005 | 24 | | GK | | 16-0 | 34-61-13 | D41089P | | 32 | | D41477P | | 5 | | ALL |
| 0006 | 24 | | GK | | 16-0 | 34-61-13 | D41089P | | 33 | | D41477P | | 6 | | ALL |
| 0007 | 24 | | GK | | 16-0 | 34-61-13 | D41089P | | 34 | | D41477P | | 7 | | ALL |
| 0008 | 24 | | GK | | 16-0 | 34-61-13 | D41089P | | 35 | | D41477P | | 8 | | ALL |
| 0009 | 24 | | GK | | 16-0 | 34-61-13 | D41089P | | 36 | | D41477P | | 9 | | ALL |
| 0010 | 24 | | GK | | 16-0 | 34-61-13 | D41089P | | 37 | | D41477P | | 11 | | ALL |
| 0011 | 24 | | GK | | 16-0 | 34-61-13 | D41089P | | 38 | | D41477P | | 12 | | ALL |
| 0012 | 24 | | GK | | 16-0 | 34-61-13 | D41089P | | 39 | | D41477P | | 13 | | ALL |
| 0013 | 24 | | GK | | 20-0 | SPARE | D41473P | | 3 | | D41309P | | 12 | | 001-099 |
| 0013 | 24 | | GK | | 20-0 | 31-31-32 | D41473P | | 3 | | D41309P | | 12 | | 115-199 |
| 0014 | 24 | | GK | | 26-0 | 31-31-61 | D41309P | | 18 | | D41319P | | 1 | | 001-099 |
| 0014 | 24 | | GK | | 28-0 | 31-31-32 | D41309P | | 18 | | D41319P | | 1 | | 115-199 |
| 0015 | 24 | | GK | | 22-0 | 31-31-61 | D41309P | | 19 | | D41093P | | 26 | | 001-099 |
| 0015 | 24 | | GK | | 21-0 | 31-31-31 | D41309P | | 19 | | D41093P | | 26 | | 115-199 |
| 0016 | 24 | | GK | | 22-0 | 31-31-61 | D41309P | | 20 | | D41093P | | 27 | | 001-099 |
| 0016 | 24 | | GK | | 21-0 | 31-31-31 | D41309P | | 20 | | D41093P | | 27 | | 115-199 |
| 0017 | 24 | | GK | | 26-0 | 31-31-61 | D41309P | | 21 | | D41319P | | 4 | | 001-099 |
| 0017 | 24 | | GK | | 28-0 | 31-31-32 | D41309P | | 21 | | D41319P | | 4 | | 115-199 |
| 0018 | 24 | | GK | | 25-0 | SPARE | D41301P | | 1 | | D41481P | | 1 | | ALL |
| 0019 | 22 | | GA | | 25-0 | 27-32-11 | D41301P | | 2 | | D41481P | | 2 | | 001-099 |
| 0019 | 24 | | GK | | 25-0 | 27-32-11 | D41301P | | 2 | | D41481P | | 2 | | 115-199 |
| 0021 | 24 | | GK | | 20-0 | 27-32-11 | D41473P | | 6 | | D41481P | | 6 | | ALL |
| 0022 | 24 | | GK | | 28-0 | 31-31-62 | D41307P | | 34 | | D41481P | | 7 | | 001-099 |
| 0022 | 24 | | GK | | 20-0 | SPARE | D41473P | | 7 | | D41481P | | 7 | | 115-199 |
| 0023 | 24 | | GK | | 16-0 | 31-51-34 | D41091P | | 6 | | D41481P | | 8 | | 009, 115-199 |
| 0024 | 24 | | GK | | 25-0 | 31-51-41 | D41481P | | 9 | | D41317P | | 7 | | 001-099 |
| 0024 | 24 | | GK | | 24-0 | 31-51-41 | D41481P | | 9 | | D41317P | | 7 | | 115-199 |
| 0025 | 24 | | GK | | 24-0 | 31-51-41 | D41325P | | 5 | | D41481P | | 10 | | ALL |
| 0026 | 24 | | GK | | 24-0 | 31-51-41 | D41325P | | 6 | | D41481P | | 11 | | ALL |
| 0027 | 24 | | GK | | 25-0 | 31-51-42 | D41301P | | 4 | | D41481P | | 12 | | ALL |
| 0028 | 24 | | GK | | 24-0 | 31-51-42 | D41325P | | 9 | | D41481P | | 13 | | ALL |
| 0029 | 24 | | GK | | 17-0 | SPARE | D41325P | | 8 | | D41317P | | 15 | | 115-199 |
| 0030 | 24 | | GK | | 25-0 | 34-53-11 | D41309P | | 48 | | D41317P | | 16 | | 115-199 |
| 0031 | 24 | | GK | | 13-0 | 24-28-11 | D41473P | | 13 | | D41317P | | 17 | | ALL |
| 0032 | 24 | | GK | | 25-0 | 31-51-33 | D41481P | | 14 | | D41317P | | 23 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 0032 | 24 | | GK | | 24-0 | 31-51-33 | D41481P | | 14 | | D41317P | 23 | | | 115-199 |
| 0033 | 24 | | GK | | 20-0 | 31-51-21 | D41473P | | 8 | | D41481P | 15 | | | ALL |
| 0034 | 24 | | GK | | 17-0 | 31-51-21 | D41097P | | 37 | | D41481P | 16 | | | ALL |
| 0035 | 24 | | GK | | 16-0 | 31-51-21 | D41091P | | 1 | | D41481P | 17 | | | ALL |
| 0036 | 24 | | GK | | 12-0 | SPARE | D41319P | | 6 | | D41317P | 24 | | | 115-199 |
| 0037 | 22 | | GA | | 19-0 | 22-12-11 | D41091P | | 22 | | D41325P | 14 | | | ALL |
| 0038 | 22 | | GA | | 19-0 | 22-12-11 | D41091P | | 23 | | D41325P | 4 | | | ALL |
| 0039 | 22 | | GA | | 19-0 | 22-12-11 | D41091P | | 24 | | D41325P | 46 | | | ALL |
| 0040 | 22 | | GA | | 15-0 | 22-12-11 | D41091P | | 25 | | D41477P | 16 | | | ALL |
| 0041 | 22 | | GA | | 15-0 | 22-12-11 | D41091P | | 26 | | D41477P | 17 | | | ALL |
| 0042 | 22 | | GA | | 16-0 | 22-14-11 | D41091P | | 27 | | D41481P | 28 | | | ALL |
| 0043 | 22 | | GA | | 16-0 | SPARE | D41091P | | 28 | | D41481P | 27 | | | ALL |
| 0044 | 22 | | GA | | 21-0 | 22-14-31 | D41473P | | 9 | | D41303P | 4 | | | ALL |
| 0045 | 22 | | GA | | 20-0 | 22-22-11 | D41091P | | 35 | | D41301P | 8 | | | ALL |
| 0046 | 22 | | GA | | 20-0 | 22-22-11 | D41091P | | 36 | | D41301P | 9 | | | ALL |
| 0047 | 24 | | GK | | 15-0 | 23-12-11 | D41319P | | 2 | | D41475P | 22 | | | 001-099 |
| 0047 | 24 | | GK | | 15-0 | 23-12-11 | D41475P | | 22 | | D41319P | 2 | | | 115-199 |
| 0048 | 24 | | GK | | 17-0 | 31-51-21 | D41097P | | 48 | | D41481P | 48 | | | ALL |
| 0049 | 22 | | GA | | 21-0 | SPARE | D41473P | | 14 | | D41311P | 2 | | | 001-099 |
| 0050 | 24 | | GK | | 10-0 | 32-61-12 | D41307P | | 8 | | D41311P | 3 | | | 001-099 |
| 0050 | 24 | | GK | | 10-0 | 32-61-12 | D41307P | | 30 | | D41311P | 37 | | | 115-199 |
| 0051 | 24 | | GK | | 17-0 | SPARE | D41317P | | 25 | | D41325P | 34 | | | 115-199 |
| 0052 | 24 | | GK | | 17-0 | SPARE | D41317P | | 26 | | D41325P | 35 | | | 115-199 |
| 0054 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 26 | | D41097P | 7 | | | ALL |
| 0055 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 27 | | D41097P | 8 | | | ALL |
| 0056 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 28 | | D41097P | 9 | | | ALL |
| 0057 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 29 | | D41097P | 10 | | | ALL |
| 0058 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 30 | | D41097P | 11 | | | ALL |
| 0059 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 31 | | D41097P | 12 | | | ALL |
| 0060 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 32 | | D41097P | 13 | | | ALL |
| 0061 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 33 | | D41097P | 14 | | | ALL |
| 0062 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 34 | | D41097P | 15 | | | ALL |
| 0063 | 24 | | GK | | 16-0 | 22-32-13 | D41477P | | 35 | | D41097P | 16 | | | ALL |
| 0065 | 24 | | GK | | 24-0 | 31-51-42 | D41325P | | 10 | | D41481P | 26 | | | ALL |
| 0066 | 24 | | GK | | 17-0 | 22-32-15 | D41473P | | 11 | | D41097P | 19 | | | ALL |
| 0067 | 24 | | GK | | 17-0 | 22-32-15 | D41473P | | 12 | | D41097P | 20 | | | ALL |
| 0068 | 22 | | GA | | 24-0 | 22-41-11 | D41095P | | 1 | | D41303P | 5 | | | ALL |
| 0069 | 22 | | GA | | 23-0 | 22-41-11 | D41097P | | 21 | | D41303P | 6 | | | ALL |
| 0070 | 22 | | GA | | 23-0 | 22-41-11 | D41097P | | 22 | | D41303P | 7 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | | 286N4471 | | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | |
| 0071 | 22 | GA | | | 22-0 | 22-41-11 | D41091P | | 43 | | D41303P | | 14 | | ALL |
| 0073 | 22 | GA | | | 20-0 | SPARE | D41091P | | 48 | | D41317P | | 30 | | ALL |
| 0074 | 22 | GA | | | 24-0 | 22-21-11 | D41099P | | 4 | | D41301P | | 22 | | ALL |
| 0075 | 22 | GA | | | 24-0 | 27-09-13 | D41879P | | 29 | | D41301P | | 24 | | ALL |
| 0076 | 22 | GA | | | 24-0 | 27-09-13 | D41879P | | 38 | | D41301P | | 23 | | ALL |
| 0077 | 22 | GA | | | 19-0 | 27-09-12 | D41473P | | 15 | | D41301P | | 25 | | ALL |
| 0078 | 22 | GA | | | 15-0 | 30-32-11 | D41473P | | 17 | | D41093P | | 9 | | ALL |
| 0079 | 22 | GA | | | 15-0 | 30-32-11 | D41473P | | 18 | | D41093P | | 10 | | ALL |
| 0080 | 24 | GK | | | 13-0 | 30-33-11 | D41473P | | 19 | | D41317P | | 34 | | ALL |
| 0081 | 22 | GA | | | 16-0 | 23-71-11 | D41319P | | 15 | | D41473P | | 24 | | ALL |
| 0082 | 22 | GA | | | 16-0 | 23-71-11 | D41319P | | 14 | | D41473P | | 25 | | ALL |
| 0083 | 24 | GK | | | 13-0 | SPARE | D41317P | | 38 | | D41473P | | 20 | | ALL |
| 0084 | 24 | GK | | | 12-0 | 21-31-11 | D41325P | | 36 | | D41473P | | 21 | | ALL |
| 0086 | 24 | GK | | | 17-0 | SPARE | D41317P | | 40 | | D41325P | | 39 | | 115-199 |
| 0087 | 22 | GA | | | 21-0 | 76-11-21 | D41473P | | 26 | | D41311P | | 1 | | ALL |
| 0088 | 24 | GK | | | 15-0 | 34-61-13 | D41477P | | 43 | | D41093P | | 4 | | ALL |
| 0089 | 24 | GK | | | 15-0 | 34-61-13 | D41477P | | 45 | | D41093P | | 5 | | ALL |
| 0090 | 24 | GK | | | 15-0 | 34-61-13 | D41477P | | 46 | | D41093P | | 6 | | ALL |
| 0091 | 24 | GK | | | 15-0 | 34-61-13 | D41477P | | 44 | | D41093P | | 7 | | ALL |
| 0093 | 24 | GK | | | 13-0 | SPARE | D41317P | | 45 | | D41473P | | 28 | | ALL |
| 0094 | 24 | GK | | | 16-0 | 34-55-11 | D41089P | | 49 | | D41473P | | 29 | | ALL |
| 0095 | 24 | GK | | | 22-0 | 34-55-11 | D41089P | | 48 | | D41309P | | 41 | | ALL |
| 0096 | 24 | GK | | | 20-0 | 34-33-11 | D41089P | | 50 | | D41325P | | 40 | | ALL |
| 0097 | 22 | GA | | | 23-0 | 34-21-11 | D41099P | | 12 | | D41317P | | 46 | | ALL |
| 0098 | 22 | GA | | | 23-0 | 34-21-11 | D41099P | | 13 | | D41317P | | 47 | | ALL |
| 0099 | 22 | GA | | | 23-0 | 34-21-11 | D41099P | | 14 | | D41317P | | 48 | | ALL |
| 0100 | 24 | GK | | | 11-0 | SPARE | D41095P | | 7 | | D41089P | | 51 | | 115-199 |
| 0101 | 24 | GK | | | 20-0 | 34-12-12 | D41879P | | 39 | | D41089P | | 52 | | ALL |
| 0102 | 24 | GK | | | 15-0 | 34-12-12 | D41473P | | 32 | | D41091P | | 49 | | ALL |
| 0103 | 24 | GK | | | 15-0 | 34-12-12 | D41473P | | 31 | | D41091P | | 50 | | ALL |
| 0104 | 22 | GA | | | 9-0 | SPARE | D41329P | | 5 | | D41325P | | 23 | | 115-199 |
| 0105 | 24 | GK | | | 9-0 | 27-51-41 | D41329P | | 6 | | D41325P | | 24 | | 001-099 |
| 0105 | 22 | GA | | | 9-0 | 27-51-41 | D41329P | | 6 | | D41325P | | 24 | | 115-199 |
| 0106 | 24 | GK | | | 9-0 | 27-51-41 | D41329P | | 7 | | D41325P | | 25 | | 001-099 |
| 0106 | 22 | GA | | | 9-0 | 27-51-41 | D41329P | | 7 | | D41325P | | 25 | | 115-199 |
| 0107 | 24 | GK | | | 9-0 | 27-51-41 | D41329P | | 8 | | D41325P | | 26 | | 001-099 |
| 0107 | 22 | GA | | | 9-0 | 27-51-41 | D41329P | | 8 | | D41325P | | 26 | | 115-199 |
| 0108 | 24 | GK | | | 9-0 | 27-51-41 | D41329P | | 9 | | D41325P | | 27 | | 001-099 |
| 0108 | 22 | GA | | | 9-0 | 27-51-41 | D41329P | | 9 | | D41325P | | 27 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 0109 | 24 | | GK | | 9-0 | 27-51-41 | D41329P | | 10 | | D41325P | 28 | | | 001-099 |
| 0109 | 22 | | GA | | 9-0 | 27-51-41 | D41329P | | 10 | | D41325P | 28 | | | 115-199 |
| 0110 | 24 | | GK | | 9-0 | 27-58-11 | D41329P | | 11 | | D41325P | 29 | | | ALL |
| 0111 | 24 | | GK | | 9-0 | 27-58-31 | D41329P | | 15 | | D41325P | 30 | | | ALL |
| 0112 | 22 | | GA | | 24-0 | SPARE | D41481P | | 18 | | D41325P | 45 | | | ALL |
| 0113 | 24 | | GK | | 15-0 | SPARE | D41473P | | 33 | | D41905P | 5 | | | 001-099 |
| 0114 | 24 | | GK | | 13-0 | 27-58-11 | D41317P | | 49 | | D41473P | 34 | | | 001-099 |
| 0114 | 22 | | GA | | 13-0 | 27-58-11 | D41317P | | 49 | | D41473P | 34 | | | 115-199 |
| 0115 | 24 | | GK | | 13-0 | 27-58-11 | D41317P | | 50 | | D41473P | 35 | | | 001-099 |
| 0115 | 22 | | GA | | 13-0 | 27-58-11 | D41317P | | 50 | | D41473P | 35 | | | 115-199 |
| 0116 | 24 | | GK | | 13-0 | 27-58-11 | D41317P | | 51 | | D41473P | 36 | | | 001-099 |
| 0116 | 22 | | GA | | 13-0 | 27-58-11 | D41317P | | 51 | | D41473P | 36 | | | 115-199 |
| 0117 | 24 | | GK | | 13-0 | 27-58-11 | D41317P | | 52 | | D41473P | 37 | | | 001-099 |
| 0117 | 22 | | GA | | 13-0 | 27-58-11 | D41317P | | 52 | | D41473P | 37 | | | 115-199 |
| 0119 | 22 | | GA | | 9-0 | 22-11-12 | D41643P | | 22 | | D41905P | 22 | | | 001-099 |
| 0119 | 22 | | GA | | 9-0 | 22-11-12 | D41905P | | 22 | | D41643P | 22 | | | 115-199 |
| 0120 | 22 | | GA | | 26-0 | 32-61-21 | D41879P | | 1 | | D41311P | 4 | | | ALL |
| 0121 | 22 | | GA | | 26-0 | 32-61-21 | D41879P | | 2 | | D41311P | 5 | | | ALL |
| 0122 | 22 | | GA | | 26-0 | 32-61-21 | D41879P | | 3 | | D41311P | 6 | | | ALL |
| 0123 | 22 | | GA | | 9-0 | 22-11-12 | D41643P | | 23 | | D41905P | 23 | | | 001-099 |
| 0123 | 22 | | GA | | 9-0 | 22-11-12 | D41905P | | 23 | | D41643P | 23 | | | 115-199 |
| 0124 | 24 | | GK | | 20-0 | SPARE | D41879P | | 40 | | D41093P | 18 | | | 115-199 |
| 0125 | 24 | | GK | | 20-0 | SPARE | D41093P | | 22 | | D41879P | 41 | | | 115-199 |
| 0126 | 22 | | GA | | 15-0 | 34-12-11 | D41093P | | 23 | | D41473P | 39 | | | ALL |
| 0127 | 22 | | GA | | 15-0 | 34-12-11 | D41093P | | 24 | | D41473P | 40 | | | ALL |
| 0128 | 24 | | GK | | 15-0 | 34-12-12 | D41473P | | 41 | | D41093P | 25 | | | ALL |
| 0129 | 22 | | GA | | 15-0 | 32-42-11 | D41093P | | 17 | | D41475P | 42 | | | ALL |
| 0130 | 22 | | GA | | 21-0 | 22-34-11 | D41879P | | 4 | | D41097P | 36 | | | ALL |
| 0131 | 24 | | GK | | 27-0 | 31-51-21 | D41311P | | 7 | | D41481P | 19 | | | 001-099 |
| 0131 | 24 | | GK | | 26-0 | 31-51-21 | D41311P | | 7 | | D41481P | 19 | | | 115-199 |
| 0132 | 24 | | GK | | 27-0 | 31-51-21 | D41311P | | 8 | | D41481P | 20 | | | 001-099 |
| 0132 | 24 | | GK | | 26-0 | 31-51-21 | D41311P | | 8 | | D41481P | 20 | | | 115-199 |
| 0133 | 24 | | GK | | 27-0 | 31-51-33 | D41311P | | 9 | | D41481P | 21 | | | 001-099 |
| 0133 | 24 | | GK | | 26-0 | 31-51-33 | D41311P | | 9 | | D41481P | 21 | | | 115-199 |
| 0134 | 24 | | GK | | 13-0 | 31-41-19 | D41473P | | 46 | | D41879P | 5 | | | 115-199 |
| 0135 | 22 | | GA | | 23-0 | SPARE | D41099P | | 15 | | D41317P | 16 | | | 001-099 |
| 0135 | 22 | | GA | | 23-0 | SPARE | D41099P | | 15 | | D41325P | 47 | | | 115-199 |
| 0136 | 22 | | GA | | 23-0 | SPARE | D41099P | | 16 | | D41317P | 8 | | | 001-099 |
| 0136 | 22 | | GA | | 23-0 | SPARE | D41099P | | 16 | | D41325P | 48 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|--|--|----------|---------|-------|------|------|--------|---------|------|------|--------|------------------|
| | | | | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 0137 | 22 | GA | | 19-0 | SPARE | D41099P | | 17 | | | D41473P | 52 | | | 001-099 |
| 0137 | 22 | GA | | 23-0 | SPARE | D41099P | | 17 | | | D41325P | 49 | | | 115-199 |
| 0138 | 22 | GA | | 23-0 | SPARE | D41099P | | 18 | | | D41325P | 50 | | | 115-199 |
| 0139 | 24 | GK | | 12-0 | 24-25-13 | D41317P | | 53 | | | D41475P | 46 | | | ALL |
| 0140 | 24 | GK | | 12-0 | 24-25-13 | D41317P | | 54 | | | D41475P | 47 | | | ALL |
| 0141 | 24 | GK | | 12-0 | 24-25-13 | D41317P | | 55 | | | D41475P | 49 | | | ALL |
| 0142 | 22 | GA | | 23-0 | SPARE | D41099P | | 22 | | | D42187P | 4 | | | 115-199 |
| 0143 | 22 | GA | | 20-0 | SPARE | D41091P | | 2 | | | D41301P | 29 | | | ALL |
| 0144 | 24 | GK | | 20-0 | 24-25-13 | D41317P | | 44 | | | D41475P | 44 | | | 001-099 |
| 0144 | 24 | GK | | 12-0 | 24-25-13 | D41317P | | 44 | | | D41475P | 44 | | | 115-199 |
| 0145 | 22 | GA | | 22-0 | SPARE | D41091P | | 55 | | | D41303P | 34 | | | ALL |
| 0146 | 24 | GK | | 15-0 | SPARE | D41093P | | 34 | | | D41473P | 47 | | | ALL |
| 0147 | 24 | GK | | 15-0 | SPARE | D41093P | | 38 | | | D41477P | 1 | | | ALL |
| 0149 | 24 | GK | | 16-0 | SPARE | D41097P | | 47 | | | D41477P | 47 | | | 001-099 |
| 0151 | 22 | GA | | 24-0 | SPARE | D41099P | | 26 | | | D41301P | 34 | | | ALL |
| 0152 | 24 | GK | | 28-0 | SPARE | D41309P | | 48 | | | D41319P | 19 | | | 001-099 |
| 0153 | 24 | GK | | 26-0 | 32-61-12 | D41311P | | 17 | | | D41879P | 9 | | | 001-099 |
| 0153 | 24 | GK | | 26-0 | 32-61-11 | D41311P | | 17 | | | D41879P | 9 | | | 115-199 |
| 0154 | 22 | GA | | 26-0 | SPARE | D41311P | | 18 | | | D41879P | 10 | | | 115-199 |
| 0155 | 24 | GK | | 26-0 | SPARE | D41311P | | 19 | | | D41879P | 11 | | | ALL |
| 0156 | 24 | GK | | 26-0 | SPARE | D41311P | | 20 | | | D41481P | 22 | | | 115-199 |
| 0157 | 24 | GK | | 26-0 | SPARE | D41311P | | 21 | | | D41481P | 23 | | | 115-199 |
| 0158 | 24 | GK | | 26-0 | SPARE | D41311P | | 22 | | | D41481P | 24 | | | 115-199 |
| 0159 | 22 | GA | | 9-0 | 22-14-31 | D41905P | | 20 | | | D41643P | 20 | | | ALL |
| 0160 | 24 | GK | | 17-0 | SPARE | D41317P | | 8 | | | D41325P | CAP | Y | | 115-199 |
| 0161 | 24 | GK | | 13-0 | SPARE | D41317P | | 9 | | | D41473P | 51 | | | 115-199 |
| 0162 | 24 | GK | | 15-0 | SPARE | D41319P | | 20 | | | D41475P | 7 | | | 001-099 |
| 0162 | 24 | GK | | 26-0 | SPARE | D41319P | | 20 | | | D41099P | 30 | | | 115-199 |
| 0163 | 24 | GK | | 26-0 | SPARE | D41319P | | 21 | | | D41099P | 31 | | | 115-199 |
| 0164 | 24 | GK | | 26-0 | SPARE | D41319P | | 22 | | | D41099P | 32 | | | 115-199 |
| 0165 | 22 | GA | | 14-0 | SPARE | D41329P | | 16 | | | D41473P | 52 | | | 115-199 |
| 0166 | 24 | GK | | 20-0 | SPARE | D41473P | | 10 | | | D41309P | 52 | | | 001-009, 115-199 |
| 0166 | 24 | GK | | 20-0 | 31-31-61 | D41473P | | 10 | | | D41309P | 52 | | | 010-099 |
| 0168 | 22 | GA | | 16-0 | SPARE | D41477P | | 50 | | | D41097P | CAP | Y | | 115-199 |
| 0170 | 24 | GK | | 20-0 | SPARE | D41481P | | 25 | | | D41473P | 53 | | | ALL |
| 0171 | 20 | GA | | 21-0 | 29-35-11 | D41879P | | 30 | | | D41097P | 50 | | | ALL |
| 0172 | 22 | GA | | 26-0 | SPARE | D41879P | | 12 | | | D41311P | 23 | | | 115-199 |
| 0173 | 22 | GA | | 26-0 | SPARE | D41879P | | 13 | | | D41311P | 24 | | | 115-199 |
| 0174 | 22 | GA | | 26-0 | SPARE | D41879P | | 14 | | | D41311P | 25 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|--|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 0175 | 20 | | GA | | 21-0 | 29-35-11 | | D41879P | | | 15 | D41097P | | | 51 | ALL |
| 0176 | 22 | | GA | | 9-0 | 22-14-31 | | D41905P | | | 21 | D41643P | | | 21 | ALL |
| 0177 | 24 | | GK | | 20-0 | SPARE | | D41879P | | | 44 | D41905P | | | 28 | 001-099 |
| 0178 | 24 | | GK | | 28-0 | SPARE | | D41309P | | | 47 | D41319P | | | 18 | 115-199 |
| 0179 | 22 | | GA | | 23-0 | 34-25-11 | | D41097P | | | 52 | D41309P | | | 45 | 001, 003-099, 115-199 |
| 0179 | 22 | | GA | | 23-0 | SPARE | | D41097P | | | 52 | D41309P | | | 45 | 002 |
| 0180 | 24 | | GK | | 27-0 | 31-51-33 | | D41311P | | | 26 | D41481P | | | 29 | 001-099 |
| 0180 | 24 | | GK | | 26-0 | 31-51-33 | | D41311P | | | 26 | D41481P | | | 29 | 115-199 |
| 0181 | 20 | | GA | | 9-0 | 22-41-11 | | D41309P | | | 46 | D41303P | | | 47 | ALL |
| 0182 | 24 | | GK | | 15-0 | 34-61-11 | | D41093P | | | 49 | D41475P | | | 1 | 001-099 |
| 0182 | 24 | | GK | | 15-0 | SPARE | | D41093P | | | 49 | D41475P | | | 1 | 115-199 |
| 0183 | 24 | | GK | | 15-0 | SPARE | | D41093P | | | 50 | D41475P | | | 2 | ALL |
| 0184 | 22 | | GA | | 20-0 | 22-14-31 | | D41879P | | | 19 | D41905P | | | 29 | ALL |
| 0185 | 24 | | GK | | 13-0 | SPARE | | D41879P | | | 16 | D41473P | | | 54 | ALL |
| 0186 | 22 | | GA | | 24-0 | 22-24-11 | | D42187P | | | 5 | D41301P | | | 36 | ALL |
| 0187 | 24 | | GK | | 12-0 | SPARE | | D41879P | | | 17 | D41475P | | | 4 | 001-099 |
| 0187 | 24 | | GK | | 12-0 | 36-11-11 | | D41879P | | | 17 | D41475P | | | 4 | 115-199 |
| 0188 | 24 | | GK | | 22-0 | SPARE | | D41879P | | | 18 | D41637P | | | 7 | 115-199 |
| 0189 | 22 | | GA | | 15-0 | 34-61-15 | | D41475P | | | 32 | D41905P | | | 38 | ALL |
| 0190 | 24 | | GK | | 12-0 | SPARE | | D41475P | | | 5 | D41879P | | | 20 | 115-199 |
| 0191 | 24 | | GK | | 26-0 | 31-31-62 | | D41307P | | | 48 | D41637P | | | 8 | 001-099 |
| 0191 | 22 | | GA | | 25-0 | 31-31-32 | | D41637P | | | 8 | D41307P | | | 10 | 115-199 |
| 0192 | 22 | | GA | | 19-0 | SPARE | | D41099P | | | 8 | D41473P | | | 42 | 001-099 |
| 0193 | 22 | | GA | | 22-0 | 31-31-32 | | D41475P | | | 6 | D41307P | | | 12 | 115-199 |
| 0194 | 22 | | GA | | 22-0 | 31-31-32 | | D41475P | | | 7 | D41307P | | | 13 | 115-199 |
| 0195 | 24 | | GK | | 11-0 | 31-31-62 | | D41307P | | | 14 | D41301P | | | 37 | 001-099 |
| 0195 | 24 | | GK | | 11-0 | 31-31-32 | | D41301P | | | 37 | D41307P | | | 14 | 115-199 |
| 0196 | 24 | | GK | | 11-0 | 31-31-62 | | D41307P | | | 15 | D41301P | | | 38 | 001-099 |
| 0196 | 24 | | GK | | 11-0 | 31-31-32 | | D41301P | | | 38 | D41307P | | | 15 | 115-199 |
| 0197 | 24 | | GK | | 11-0 | 31-31-62 | | D41307P | | | 16 | D41301P | | | 39 | 001-099 |
| 0197 | 24 | | GK | | 11-0 | 31-31-32 | | D41301P | | | 39 | D41307P | | | 16 | 115-199 |
| 0198 | 24 | | GK | | 11-0 | 31-31-62 | | D41307P | | | 17 | D41301P | | | 40 | 001-099 |
| 0198 | 24 | | GK | | 11-0 | 31-31-32 | | D41301P | | | 40 | D41307P | | | 17 | 115-199 |
| 0199 | 22 | | GA | | 22-0 | 31-31-32 | | D41307P | | | 18 | D41475P | | | 8 | 115-199 |
| 0200 | 24 | | GK | | 11-0 | 31-31-62 | | D41307P | | | 19 | D41301P | | | 41 | 001-099 |
| 0200 | 24 | | GK | | 11-0 | 31-31-32 | | D41301P | | | 41 | D41307P | | | 19 | 115-199 |
| 0201 | 24 | | GK | | 8-0 | 21-31-21 | | D42187P | | | 13 | D41327P | | | 4 | ALL |
| 0202 | 22 | | GA | | 22-0 | 22-14-31 | | D41095P | | | 16 | D41879P | | | 23 | ALL |
| 0203 | 22 | | GA | | 24-0 | 27-41-11 | | D42187P | | | 19 | D41301P | | | 42 | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 6

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | |
| 0208 | 22 | GA | | | 10-0 | 22-15-12 | D41097P | 35 | | | D41093P | 8 | | | ALL |
| 0209 | 22 | GA | | | 11-0 | 22-15-12 | D41093P | 43 | | | D41095P | 34 | | | ALL |
| 0210 | 22 | GA | | | 23-0 | SPARE | D41095P | | CAP | Y | D41327P | 9 | | | 115-199 |
| 0211 | 22 | GA | | | 22-0 | 22-41-11 | D41095P | 36 | | | D41879P | 27 | | | ALL |
| 0213 | 24 | GK | | | 24-0 | 34-46-11 | D41311P | 10 | | | D41097P | 49 | | | ALL |
| 0216 | 22 | GA | | | 10-0 | SPARE | D41307P | 26 | | | D41311P | 34 | | | 115-199 |
| 0217 | 24 | GK | | | 10-0 | 32-61-12 | D41307P | 10 | | | D41311P | 30 | | | 001-099 |
| 0217 | 22 | GA | | | 10-0 | 32-61-12 | D41307P | 27 | | | D41311P | 30 | | | 115-199 |
| 0218 | 22 | GA | | | 10-0 | SPARE | D41307P | 28 | | | D41311P | 35 | | | 115-199 |
| 0219 | 22 | GA | | | 10-0 | 32-61-12 | D41307P | 12 | | | D41311P | 16 | | | 001-099 |
| 0219 | 24 | GK | | | 10-0 | 32-61-12 | D41307P | 29 | | | D41311P | 36 | | | 115-199 |
| 0220 | 24 | GK | | | 26-0 | 32-61-12 | D41879P | 33 | | | D41311P | 31 | | | 001-099 |
| 0220 | 24 | GK | | | 26-0 | 32-61-11 | D41879P | 33 | | | D41311P | 31 | | | 115-199 |
| 0221 | 22 | GA | | | 26-0 | 32-61-12 | D41879P | 34 | | | D41311P | 11 | | | 001-099 |
| 0221 | 22 | GA | | | 26-0 | 32-61-11 | D41879P | 34 | | | D41311P | 32 | | | 115-199 |
| 0224 | 24 | GK | | | 16-0 | 31-51-34 | D41905P | 47 | | | D41481P | 36 | | | 009 |
| 0224 | 24 | GK | | | 16-0 | 31-51-34 | D41905P | 13 | | | D41481P | 36 | | | 115-199 |
| 0225 | 22 | GA | | | 24-0 | 27-23-21 | D41879P | 35 | | | D41477P | 10 | | | 001-099 |
| 0225 | 22 | GA | | | 23-0 | 27-23-21 | D41879P | 35 | | | D41477P | 10 | | | 115-199 |
| 0226 | 22 | GA | | | 24-0 | 27-23-21 | D41879P | 36 | | | D41477P | 14 | | | 001-099 |
| 0226 | 22 | GA | | | 23-0 | 27-23-21 | D41879P | 36 | | | D41477P | 14 | | | 115-199 |
| 0227 | 22 | GA | | | 24-0 | 27-23-21 | D41879P | 37 | | | D41477P | 15 | | | 001-099 |
| 0227 | 22 | GA | | | 23-0 | 27-23-21 | D41879P | 37 | | | D41477P | 15 | | | 115-199 |
| 0228 | 22 | GA | | | 19-0 | 27-23-21 | D41475P | 3 | | | D41477P | 41 | | | 001-099 |
| 0228 | 22 | GA | | | 18-0 | 27-23-21 | D41475P | 3 | | | D41477P | 41 | | | 115-199 |
| 0229 | 22 | GA | | | 23-0 | 27-23-21 | D41477P | 42 | | | D42187P | 6 | | | ALL |
| 0230 | 22 | GA | | | 23-0 | 27-23-21 | D41477P | 53 | | | D42187P | 7 | | | ALL |
| 0231 | 22 | GA | | | 23-0 | 27-23-21 | D41477P | 54 | | | D42187P | 8 | | | ALL |
| 0232 | 22 | GA | | | 23-0 | 27-23-21 | D41477P | 55 | | | D42187P | 9 | | | ALL |
| 0234 | 22 | GA | | | 9-0 | SPARE | D41905P | 6 | | | D41643P | 6 | | | 001-099 |
| 0236 | 24 | GK | | | 12-0 | 21-33-12 | D41475P | 43 | | | D41879P | 43 | | | ALL |
| 0237 | 22 | GA | | | 11-0 | 22-14-21 | D41905P | 19 | | | D41095P | 5 | | | ALL |
| 0238 | 22 | GA | | | 11-0 | 22-14-21 | D41905P | 18 | | | D41095P | 6 | | | ALL |
| 0239 | 22 | GA | | | 9-0 | 22-14-31 | D41095P | 10 | | | D41643P | 3 | | | ALL |
| 0240 | 22 | GA | | | 15-0 | 22-14-31 | D41475P | 45 | | | D41905P | 24 | | | ALL |
| 0243 | 20 | GA | | | 23-0 | 29-35-11 | D41879P | 28 | | | D41637P | 9 | | | 001-099 |
| 0243 | 20 | GA | | | 22-0 | 29-35-11 | D41879P | 28 | | | D41637P | 9 | | | 115-199 |
| 0248 | 24 | GK | | | 13-0 | 31-41-19 | D41473P | 46 | | | D41879P | 5 | | | 001-099 |
| 0251 | 22 | GA | | | 10-0 | 32-61-12 | D41307P | 11 | | | D41311P | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 7

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4471 | 286N4471 | | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | | |
| 0251 | 24 | | GK | | 10-0 | 32-61-12 | D41307P | 11 | | | | D41311P | 38 | | | 115-199 | |
| 0252 | 22 | | GA | | 14-0 | 74-31-11 | D41329P | 20 | | | | D41473P | 30 | | | 115-199 | |
| 0253 | 22 | | GA | | 12-0 | SPARE | D42187P | 18 | | | | D41473P | 38 | | | 001-099 | |
| 0253 | 22 | | GA | | 12-0 | 74-31-11 | D42187P | 18 | | | | D41473P | 38 | | | 115-199 | |
| 0256 | 24 | | GK | | 8-0 | 73-21-12 | D41879P | 48 | | | | SM00001 | | 9 | | 001-099 | |
| 0256 | 24 | | GK | | 8-0 | 73-21-12 | SM00001 | | 9 | | | D41879P | 48 | | | 115-199 | |
| 0257 | 24 | | GK | | 23-0 | 73-21-12 | D41637P | 12 | | | | D41879P | 49 | | | 001-099 | |
| 0257 | 24 | | GK | | 22-0 | 73-21-12 | D41637P | 12 | | | | D41879P | 49 | | | 115-199 | |
| 0268 | 22 | | GA | | 18-0 | 30-34-21 | D41475P | 36 | | | | D41477P | 48 | | | 001-099 | |
| 0268 | 22 | | GA | | 18-0 | 30-34-21 | D41477P | 48 | | | | D41475P | 36 | | | 115-199 | |
| 0269 | 22 | | GA | | 19-0 | 30-34-21 | D41475P | 37 | | | | D41477P | 49 | | | 001-099 | |
| 0269 | 22 | | GA | | 18-0 | 30-34-21 | D41477P | 49 | | | | D41475P | 37 | | | 115-199 | |
| 0270 | 22 | | GA | | 19-0 | 30-34-21 | D41475P | 35 | | | | D41477P | 51 | | | 001-099 | |
| 0270 | 22 | | GA | | 18-0 | 30-34-21 | D41477P | 51 | | | | D41475P | 35 | | | 115-199 | |
| 0271 | 22 | | GA | | 13-0 | SPARE | D41329P | 23 | | | | D41475P | 38 | | | 001-099 | |
| 0279 | 20 | | GA | | 9-0 | SPARE | D41309P | 34 | | | | D41303P | 35 | | | 001-099 | |
| 0281 | 24 | | GK | | 9-0 | SPARE | D41329P | 3 | | | | D42187P | 39 | | | 001-099 | |
| 0282 | 24 | | GK | | 20-0 | 34-51-11 | D43003P | 11 | | | | D43001P | 11 | | | 001-099 | |
| 0283 | 22 | | GA | | 20-0 | SPARE | D43003P | 15 | | | | D43001P | 15 | | | 001-099 | |
| 0284 | 24 | | GK | | 20-0 | SPARE | D43003P | 3 | | | | D43001P | 16 | | | 001-099 | |
| 0285 | 22 | | GA | | 24-0 | SPARE | D41301P | 12 | | | | D42187P | 22 | | | 001-099 | |
| 0286 | 22 | | GA | | 20-0 | 34-51-11 | D43003P | 4 | | | | D43001P | 4 | | | 001-099 | |
| 0287 | 22 | | GA | | 10-0 | SPARE | D41307P | 5 | | | | D41311P | 24 | | | 001-009 | |
| 0287 | 22 | | GA | | 10-0 | SPARE | D41307P | 5 | | | | D41311P | CAP | Y | | 010-099 | |
| 0288 | 24 | | GK | | 6-0 | 73-21-12 | D41475P | 48 | | | | SM00001 | | 9 | | ALL | |
| 0289 | 24 | | GK | | 16-0 | 73-21-12 | D41637P | 11 | | | | SM00001 | | 9 | | ALL | |
| 0327 | 22 | | GA | | 19-0 | 34-45-01 | D43003P | 1 | | | | D41325P | 7 | | | 001-002, 115-199 | |
| 0327 | 22 | | GA | | 19-0 | SPARE | D43003P | 1 | | | | D41325P | 7 | | | 003-099 | |
| 0328 | 22 | | GA | | 22-0 | 34-45-01 | D43003P | 2 | | | | D41311P | 12 | | | ALL | |
| 0329 | 24 | | GK | | 9-0 | 34-45-02 | D41643P | 25 | | | | D41905P | 13 | | | 001, 003-099 | |
| 0329 | 24 | | GK | | 9-0 | SPARE | D41643P | 25 | | | | D41905P | 13 | | | 002 | |
| 0329 | 24 | | GK | | 8-0 | 34-45-02 | D41643P | 25 | | | | D43003P | 30 | | | 115-199 | |
| 0330 | 24 | | GK | | 9-0 | 34-45-02 | D41643P | 26 | | | | D41905P | 14 | | | 001, 003-099 | |
| 0330 | 24 | | GK | | 9-0 | SPARE | D41643P | 26 | | | | D41905P | 14 | | | 002 | |
| 0330 | 24 | | GK | | 8-0 | 34-45-02 | D41643P | 26 | | | | D43003P | 31 | | | 115-199 | |
| 0331 | 24 | | GK | | 9-0 | 34-45-02 | D41643P | 27 | | | | D41905P | 15 | | | 001, 003-099 | |
| 0331 | 24 | | GK | | 9-0 | SPARE | D41643P | 27 | | | | D41905P | 15 | | | 002 | |
| 0331 | 24 | | GK | | 8-0 | 34-45-02 | D41643P | 27 | | | | D43003P | 32 | | | 115-199 | |
| 0332 | 24 | | GK | | 9-0 | 34-45-02 | D41643P | 28 | | | | D41905P | 11 | | | 001, 003-099 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 8

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | | | |
| 0332 | 24 | GK | | | 9-0 | SPARE | D41643P | 28 | | | D41905P | 11 | | | 002 |
| 0332 | 24 | GK | | | 8-0 | 34-45-02 | D41643P | 28 | | | D43003P | 33 | | | 115-199 |
| 0333 | 22 | GA | | | 9-0 | 22-13-11 | D41905P | 10 | | | D41643P | 32 | | | 001-099 |
| 0333 | 22 | GA | | | 8-0 | 22-13-11 | D43003P | 42 | | | D41643P | 32 | | | 115-199 |
| 0334 | 22 | GA | | | 8-0 | 34-31-11 | D41643P | 39 | | | D43003P | 24 | | | ALL |
| 0336 | 22 | GA | | | 8-0 | 34-31-11 | D41643P | 41 | | | D43003P | 23 | | | ALL |
| 0339 | 22 | GA | | | 12-0 | 27-23-11 | D41475P | 39 | | | D42187P | 39 | | | 115-199 |
| 0340 | 22 | GA | | | 12-0 | 27-23-11 | D41475P | 40 | | | D42187P | 40 | | | 115-199 |
| 0341 | 22 | GA | | | 12-0 | 27-23-11 | D41475P | 41 | | | D42187P | 41 | | | 115-199 |
| 0347 | 22 | GA | | | 11-0 | 31-31-31 | D41301P | 3 | | | D41307P | 48 | | | 115-199 |
| 0348 | 22 | GA | | | 9-0 | 31-31-62 | D41301P | 47 | | | D41309P | 1 | | | 001-099 |
| 0349 | 22 | GA | | | 9-0 | 31-31-62 | D41301P | 48 | | | D41309P | 2 | | | 001-099 |
| 0350 | 22 | GA | | | 9-0 | 31-31-62 | D41301P | 49 | | | D41309P | 3 | | | 001-099 |
| 0417 | 22 | GA | | | 8-3 | 31-31-61 | D41311P | 23 | | | D41307P | 2 | | | 010-099 |
| 0418 | 22 | GA | | | 8-3 | 31-31-61 | D41311P | 24 | | | D41307P | 1 | | | 010-099 |
| 0472 | 22 | CQ | | | 40-0 | 34-22-18 | D41643P | 40 | | | D41473P | 7 | | | 002 |
| 0473 | 22 | CQ | | | 40-0 | 34-22-18 | D41643P | 24 | | | D41307P | 28 | | | 002 |
| 0476 | 22 | CQ | | | 30-0 | 34-22-18 | D41643P | 10 | | | D41089P | 51 | | | 002 |
| 0553 | 22 | GA | | | 12-0 | 34-12-61 | D03925 | 2 | | | D42175P | 14 | | | ALL |
| 0554 | 22 | GA | | | 12-0 | 34-12-61 | D03925 | 1 | | | D42175P | 15 | | | ALL |
| 0555 | 22 | GA | | | 12-0 | 34-12-61 | D03925 | 5 | | | D42175P | 1 | | | ALL |
| 0556 | 22 | GA | | | 12-0 | 34-12-61 | D03925 | 6 | | | D42175P | 2 | | | ALL |
| 0557 | 22 | GA | | | 12-0 | 34-12-61 | D03925 | 14 | | | D42175P | 9 | | | ALL |
| 0558 | 22 | GA | | | 12-0 | 34-12-61 | D03925 | 13 | | | D42175P | 10 | | | ALL |
| 0559 | 22 | GA | | | 11-0 | 34-12-61 | D03925 | 15 | | | D42221P | 1 | | | ALL |
| 0560 | 22 | GA | | | 11-0 | 34-12-61 | D03925 | 18 | | | D42221P | 5 | | | ALL |
| 0561 | 22 | GA | | | 11-0 | 34-12-61 | D03925 | 17 | | | D42221P | 6 | | | ALL |
| 0562 | 22 | GA | | | 12-0 | 34-12-61 | D03925 | 16 | | | D42175P | 16 | | | ALL |
| 0564 | 22 | GA | | | 12-0 | 34-12-61 | D42175P | 17 | | | D41095P | 35 | | | ALL |
| 0807 | 22 | PA | | | 14-6 | 34-61-15 | D41475P | 33 | | | D41905P | 28 | | | 115-199 |
| 0808 | 22 | PA | | | 20-0 | 34-61-16 | D43023P | 2 | | | D43019P | 2 | | | 115-199 |
| 0809 | 22 | PA | | | 20-0 | 34-61-16 | D43023P | 1 | | | D43019P | 1 | | | 115-199 |
| 0810 | 22 | PA | | | 20-0 | 34-61-16 | D43023P | 18 | | | D43019P | 18 | | | 115-199 |
| 0811 | 22 | PA | | | 20-0 | 34-61-16 | D43023P | 19 | | | D43019P | 19 | | | 115-199 |
| 2001B | 24 | GL | AJ | | 20-0 | SPARE | D41473P | 2 | | | D41309P | 11 | | | 001-099 |
| 2001B | 24 | GL | AJ | | 20-0 | 31-31-32 | D41473P | 2 | | | D41309P | 11 | | | 115-199 |
| 2001R | 24 | GL | AJ | | 0-0 | SPARE | D41473P | 1 | | | D41309P | 10 | | | 001-099 |
| 2001R | 24 | GL | AJ | | 0-0 | 31-31-32 | D41473P | 1 | | | D41309P | 10 | | | 115-199 |
| 2002B | 24 | GL | AK | | 20-0 | SPARE | D41473P | 5 | | | D41309P | 14 | | | 001-009 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 9

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 2002B | 24 | GL | AK | | 20-0 | 31-31-51 | D41473P | | 5 | | D41309P | 14 | | | 010-099 |
| 2002B | 24 | GL | AK | | 20-0 | 31-31-32 | D41473P | | 5 | | D41309P | 14 | | | 115-199 |
| 2002R | 24 | GL | AK | | 0-0 | SPARE | D41473P | | 4 | | D41309P | 13 | | | 001-009 |
| 2002R | 24 | GL | AK | | 0-0 | 31-31-51 | D41473P | | 4 | | D41309P | 13 | | | 010-099 |
| 2002R | 24 | GL | AK | | 0-0 | 31-31-32 | D41473P | | 4 | | D41309P | 13 | | | 115-199 |
| 2003B | 24 | GL | AL | | 9-0 | SPARE | D41301P | | 27 | | D41309P | 16 | | | 001-009 |
| 2003B | 24 | GL | AL | | 9-0 | 31-31-51 | D41301P | | 27 | | D41309P | 16 | | | 010-099 |
| 2003B | 24 | GL | AL | | 9-0 | 31-31-32 | D41301P | | 27 | | D41309P | 16 | | | 115-199 |
| 2003R | 24 | GL | AL | | 0-0 | SPARE | D41301P | | 26 | | D41309P | 15 | | | 001-009 |
| 2003R | 24 | GL | AL | | 0-0 | 31-31-51 | D41301P | | 26 | | D41309P | 15 | | | 010-099 |
| 2003R | 24 | GL | AL | | 0-0 | 31-31-32 | D41301P | | 26 | | D41309P | 15 | | | 115-199 |
| 2004B | 24 | GL | AX | | 23-0 | SPARE | D41477P | | 19 | | D41325P | 19 | | | 115-199 |
| 2004R | 24 | GL | AX | | 0-0 | SPARE | D41477P | | 18 | | D41325P | 18 | | | 115-199 |
| 2005B | 24 | GL | AY | | 23-0 | SPARE | D41477P | | 21 | | D41325P | 21 | | | 115-199 |
| 2005R | 24 | GL | AY | | 0-0 | SPARE | D41477P | | 20 | | D41325P | 20 | | | 115-199 |
| 2006B | 22 | GB | DB | | 20-0 | 22-12-11 | D41905P | | 37 | | D41301P | 11 | | | ALL |
| 2006R | 22 | GB | DB | | 0-0 | 22-12-11 | D41905P | | 36 | | D41301P | 10 | | | ALL |
| 2007B | 22 | GB | BC | | 24-0 | SPARE | D41477P | | 25 | | D41301P | 15 | | | ALL |
| 2007R | 22 | GB | BC | | 0-0 | SPARE | D41477P | | 24 | | D41301P | 14 | | | ALL |
| 2008B | 24 | GL | BQ | | 12-0 | 21-31-11 | D41325P | | 38 | | D41473P | 23 | | | ALL |
| 2008R | 24 | GL | BQ | | 0-0 | 21-31-11 | D41325P | | 37 | | D41473P | 22 | | | ALL |
| 2009B | 24 | GL | CL | | 12-0 | SPARE | D41319P | | 23 | | D41879P | 21 | | | 115-199 |
| 2009R | 24 | GL | CL | | 0-0 | SPARE | D41319P | | 24 | | D41879P | 22 | | | 115-199 |
| 2010B | 22 | GB | CR | | 24-0 | 22-24-11 | D41477P | | 3 | | D41301P | 44 | | | ALL |
| 2010R | 22 | GB | CR | | 0-0 | 22-24-11 | D41477P | | 2 | | D41301P | 43 | | | ALL |
| 2011B | 24 | GL | CS | | 21-0 | 22-32-13 | D42187P | | 21 | | D41097P | 18 | | | ALL |
| 2011R | 24 | GL | CS | | 0-0 | 22-32-13 | D42187P | | 20 | | D41097P | 17 | | | ALL |
| 2012B | 24 | GL | CT | | 8-0 | 21-31-21 | D42187P | | 15 | | D41327P | 6 | | | ALL |
| 2012R | 24 | GL | CT | | 0-0 | 21-31-21 | D42187P | | 14 | | D41327P | 5 | | | ALL |
| 2013B | 24 | GL | CU | | 8-0 | 21-31-21 | D42187P | | 17 | | D41327P | 8 | | | ALL |
| 2013R | 24 | GL | CU | | 0-0 | 21-31-21 | D42187P | | 16 | | D41327P | 7 | | | ALL |
| 2014B | 24 | GL | CW | | 22-0 | SPARE | D41307P | | 25 | | D41475P | 10 | | | 115-199 |
| 2014R | 24 | GL | CW | | 0-0 | SPARE | D41307P | | 24 | | D41475P | 9 | | | 115-199 |
| 2015B | 20 | GB | DF | | 20-0 | 29-32-41 | D41879P | | 32 | | D41643P | 2 | | | 001-099 |
| 2015B | 20 | GB | DF | | 20-0 | 29-32-41 | D41643P | | 2 | | D41879P | 32 | | | 115-199 |
| 2015R | 20 | GB | DF | | 0-0 | 29-32-41 | D41879P | | 31 | | D41643P | 1 | | | 001-099 |
| 2015R | 20 | GB | DF | | 0-0 | 29-32-41 | D41643P | | 1 | | D41879P | 31 | | | 115-199 |
| 2016B | 24 | GL | CM | | 8-0 | SPARE | D41327P | | 12 | | D42187P | 4 | | | 001-099 |
| 2016R | 24 | GL | CM | | 0-0 | SPARE | D41327P | | 11 | | D42187P | 3 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 10

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 2017B | 22 | | GB | DM | 25-0 | 31-51-43 | D41301P | 46 | | | D41481P | 42 | | | ALL |
| 2017R | 22 | | GB | DM | 0-0 | 31-51-43 | D41301P | 45 | | | D41481P | 41 | | | ALL |
| 2501B | 24 | | G2 | BS | 22-0 | 23-51-13 | D41319P | 8 | | | D41643P | 30 | | | 001-099 |
| 2501B | 24 | | G2 | BS | 23-0 | 23-51-13 | D41319P | 9 | | | D41643P | 30 | | | 115-199 |
| 2501R | 24 | | G2 | BS | 0-0 | 23-51-13 | D41319P | 7 | | | D41643P | 29 | | | 001-099 |
| 2501R | 24 | | G2 | BS | 0-0 | 23-51-13 | D41319P | 8 | | | D41643P | 29 | | | 115-199 |
| 2501Z | | | | BS | 0-0 | 23-51-13 | D41319P | 9 | | | D41643P | 31 | | | 001-099 |
| 2501Z | | | | BS | 0-0 | 23-51-13 | D41319P | 7 | | | D41643P | 31 | | | 115-199 |
| 2502B | 24 | | G2 | BW | 9-0 | 27-58-31 | D41329P | 13 | | | D41325P | 32 | | | ALL |
| 2502R | 24 | | G2 | BW | 0-0 | 27-58-31 | D41329P | 14 | | | D41325P | 31 | | | ALL |
| 2502Z | | | | BW | 0-0 | 27-58-31 | D41329P | 12 | | | D41325P | 33 | | | ALL |
| 2511B | 24 | | G2 | FU | 12-6 | 34-12-61 | D03925 | 11 | | | D42175P | 4 | | | ALL |
| 2511R | 24 | | G2 | FU | 0-0 | 34-12-61 | D03925 | 8 | | | D42175P | 3 | | | ALL |
| 2511Z | | | | FU | 0-0 | 34-12-61 | D03925 | DED | | | D42175P | 5 | | | ALL |
| 2512B | 24 | | G2 | FW | 12-6 | 34-12-61 | D03925 | 10 | | | D42175P | 7 | | | 001-099 |
| 2512B | 24 | | G2 | FA | 12-6 | 34-12-61 | D03925 | 10 | | | D42175P | 7 | | | 115-199 |
| 2512R | 24 | | G2 | FW | 0-0 | 34-12-61 | D03925 | 7 | | | D42175P | 6 | | | 001-099 |
| 2512R | 24 | | G2 | FA | 0-0 | 34-12-61 | D03925 | 7 | | | D42175P | 6 | | | 115-199 |
| 2512Z | | | | FW | 0-0 | 34-12-61 | D03925 | DED | | | D42175P | 8 | | | 001-099 |
| 2512Z | | | | FA | 0-0 | 34-12-61 | D03925 | DED | | | D42175P | 8 | | | 115-199 |
| 2513B | 24 | | G2 | FV | 12-6 | 34-12-61 | D03925 | 12 | | | D42221P | 3 | | | 001-099 |
| 2513B | 24 | | G2 | FB | 12-6 | 34-12-61 | D03925 | 12 | | | D42221P | 3 | | | 115-199 |
| 2513R | 24 | | G2 | FV | 0-0 | 34-12-61 | D03925 | 9 | | | D42221P | 2 | | | 001-099 |
| 2513R | 24 | | G2 | FB | 0-0 | 34-12-61 | D03925 | 9 | | | D42221P | 2 | | | 115-199 |
| 2513Z | | | | FV | 0-0 | 34-12-61 | D03925 | DED | | | D42221P | 4 | | | 001-099 |
| 2513Z | | | | FB | 0-0 | 34-12-61 | D03925 | DED | | | D42221P | 4 | | | 115-199 |
| 2514B | 24 | | G2 | WW | 12-0 | 34-12-62 | D41095P | 29 | | | D42175P | 12 | | | 001-099 |
| 2514B | 24 | | G2 | FC | 12-0 | 34-12-62 | D41095P | 26 | | | D42175P | 12 | | | 115-199 |
| 2514R | 24 | | G2 | WW | 0-0 | 34-12-62 | D41095P | 27 | | | D42175P | 11 | | | 001-099 |
| 2514R | 24 | | G2 | FC | 0-0 | 34-12-62 | D41095P | 27 | | | D42175P | 11 | | | 115-199 |
| 2514Z | | | | WW | 0-0 | 34-12-62 | D41095P | 28 | | | D42175P | 13 | | | 001-099 |
| 2514Z | | | | FC | 0-0 | 34-12-62 | D41095P | 28 | | | D42175P | 13 | | | 115-199 |
| 3501B | 24 | | G3 | BT | 28-0 | 23-51-12 | D41319P | 11 | | | D41309P | 38 | | | ALL |
| 3501R | 24 | | G3 | BT | 0-0 | 23-51-12 | D41319P | 12 | | | D41309P | 39 | | | ALL |
| 3501Y | 24 | | G3 | BT | 0-0 | 23-51-12 | D41319P | 10 | | | D41309P | 37 | | | ALL |
| 3501Z | | | | BT | 0-0 | 23-51-12 | D41319P | 13 | | | D41309P | 40 | | | ALL |
| 5001B | 24 | | G2 | AA | 20-0 | 31-41-12 | D41317P | 2 | | | D41089P | 2 | | | ALL |
| 5001R | 24 | | G2 | AA | 0-0 | 31-41-12 | D41317P | 1 | | | D41089P | 1 | | | ALL |
| 5001Z | | | | AA | 0-0 | 31-41-12 | D41317P | 3 | | | D41089P | 3 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 11

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | |
| 5002B | 24 | | G2 | AB | 20-0 | 31-41-12 | D41317P | | 5 | | D41089P | | 5 | | ALL |
| 5002R | 24 | | G2 | AB | 0-0 | 31-41-12 | D41317P | | 4 | | D41089P | | 4 | | ALL |
| 5002Z | | | | AB | 0-0 | 31-41-12 | D41317P | | 6 | | D41089P | | 6 | | ALL |
| 5003B | 24 | | G2 | AC | 22-0 | 34-61-12 | D41309P | | 8 | | D41089P | | 8 | | ALL |
| 5003R | 24 | | G2 | AC | 0-0 | 34-61-12 | D41309P | | 7 | | D41089P | | 7 | | ALL |
| 5003Z | | | | AC | 0-0 | 34-61-12 | D41309P | | 9 | | D41089P | | 9 | | ALL |
| 5004B | 24 | | G2 | AD | 20-0 | 34-61-14 | D41317P | | 11 | | D41089P | | 11 | | ALL |
| 5004R | 24 | | G2 | AD | 0-0 | 34-61-14 | D41317P | | 10 | | D41089P | | 10 | | ALL |
| 5004Z | | | | AD | 0-0 | 34-61-14 | D41317P | | 12 | | D41089P | | 12 | | ALL |
| 5005B | 24 | | G2 | AE | 23-0 | 34-61-14 | D41311P | | 14 | | D41089P | | 14 | | ALL |
| 5005R | 24 | | G2 | AE | 0-0 | 34-61-14 | D41311P | | 13 | | D41089P | | 13 | | ALL |
| 5005Z | | | | AE | 0-0 | 34-61-14 | D41311P | | 15 | | D41089P | | 15 | | ALL |
| 5006B | 24 | | G2 | AF | 20-0 | 34-61-15 | D41317P | | 20 | | D41089P | | 20 | | ALL |
| 5006R | 24 | | G2 | AF | 0-0 | 34-61-15 | D41317P | | 19 | | D41089P | | 19 | | ALL |
| 5006Z | | | | AF | 0-0 | 34-61-15 | D41317P | | 18 | | D41089P | | 18 | | ALL |
| 5007B | 24 | | G2 | AG | 22-0 | SPARE | D41089P | | 24 | | D41309P | | 2 | | 115-199 |
| 5007R | 24 | | G2 | AG | 0-0 | SPARE | D41089P | | 23 | | D41309P | | 1 | | 115-199 |
| 5007Z | | | | AG | 0-0 | SPARE | D41089P | | 25 | | D41309P | | 3 | | 115-199 |
| 5008B | 24 | | G2 | AH | 22-0 | 34-22-19 | D41089P | | 27 | | D41309P | | 5 | | ALL |
| 5008R | 24 | | G2 | AH | 0-0 | 34-22-19 | D41089P | | 26 | | D41309P | | 4 | | ALL |
| 5008Z | | | | AH | 0-0 | 34-22-19 | D41089P | | 28 | | D41309P | | 6 | | ALL |
| 5009B | 24 | | G2 | AI | 20-0 | 34-33-11 | D41089P | | 30 | | D41325P | | 3 | | ALL |
| 5009R | 24 | | G2 | AI | 0-0 | 34-33-11 | D41089P | | 29 | | D41325P | | 2 | | ALL |
| 5009Z | | | | AI | 0-0 | 34-33-11 | D41089P | | 31 | | D41325P | | 1 | | ALL |
| 5010B | 24 | | G2 | AM | 22-0 | 34-53-11 | D41309P | | 23 | | D41089P | | 43 | | ALL |
| 5010R | 24 | | G2 | AM | 0-0 | 34-53-11 | D41309P | | 22 | | D41089P | | 42 | | ALL |
| 5010Z | | | | AM | 0-0 | 34-53-11 | D41309P | | 24 | | D41089P | | 44 | | ALL |
| 5011B | 24 | | G2 | AN | 22-0 | 34-53-21 | D41303P | | 2 | | D41089P | | 46 | | ALL |
| 5011R | 24 | | G2 | AN | 0-0 | 34-53-21 | D41303P | | 1 | | D41089P | | 45 | | ALL |
| 5011Z | | | | AN | 0-0 | 34-53-21 | D41303P | | 3 | | D41089P | | 47 | | ALL |
| 5012B | 24 | | G2 | AO | 16-0 | 27-32-11 | D41091P | | 4 | | D41481P | | 4 | | ALL |
| 5012R | 24 | | G2 | AO | 0-0 | 27-32-11 | D41091P | | 3 | | D41481P | | 3 | | ALL |
| 5012Z | | | | AO | 0-0 | 27-32-11 | D41091P | | 5 | | D41481P | | 5 | | ALL |
| 5013B | 24 | | G2 | AP | 21-0 | 31-31-41 | D41091P | | 8 | | D41309P | | 26 | | 001-099 |
| 5013B | 24 | | G2 | AP | 21-0 | 31-31-21 | D41091P | | 8 | | D41309P | | 26 | | 115-199 |
| 5013R | 24 | | G2 | AP | 0-0 | 31-31-41 | D41091P | | 7 | | D41309P | | 25 | | 001-099 |
| 5013R | 24 | | G2 | AP | 0-0 | 31-31-21 | D41091P | | 7 | | D41309P | | 25 | | 115-199 |
| 5013Z | | | | AP | 0-0 | 31-31-41 | D41091P | | 9 | | D41309P | | 27 | | 001-099 |
| 5013Z | | | | AP | 0-0 | 31-31-21 | D41091P | | 9 | | D41309P | | 27 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 12

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 5014B | 24 | G2 | AQ | | 22-0 | 31-31-43 | D41091P | 11 | | | D41309P | 29 | | | 001-099 |
| 5014B | 24 | G2 | AQ | | 21-0 | 31-31-21 | D41091P | 11 | | | D41309P | 29 | | | 115-199 |
| 5014R | 24 | G2 | AQ | | 0-0 | 31-31-43 | D41091P | 10 | | | D41309P | 28 | | | 001-099 |
| 5014R | 24 | G2 | AQ | | 0-0 | 31-31-21 | D41091P | 10 | | | D41309P | 28 | | | 115-199 |
| 5014Z | | | AQ | | 0-0 | 31-31-43 | D41091P | 12 | | | D41309P | 30 | | | 001-099 |
| 5014Z | | | AQ | | 0-0 | 31-31-21 | D41091P | 12 | | | D41309P | 30 | | | 115-199 |
| 5015B | 24 | G2 | AR | | 13-0 | 31-31-41 | D41091P | 13 | | | D41637P | 1 | | | 001-099 |
| 5015B | 24 | G2 | AR | | 14-0 | 31-31-21 | D41091P | 13 | | | D41637P | 1 | | | 115-199 |
| 5015R | 24 | G2 | AR | | 0-0 | 31-31-41 | D41091P | 14 | | | D41637P | 2 | | | 001-099 |
| 5015R | 24 | G2 | AR | | 0-0 | 31-31-21 | D41091P | 14 | | | D41637P | 2 | | | 115-199 |
| 5015Z | | | AR | | 0-0 | 31-31-41 | D41091P | 15 | | | D41637P | 3 | | | 001-099 |
| 5015Z | | | AR | | 0-0 | 31-31-21 | D41091P | 15 | | | D41637P | 3 | | | 115-199 |
| 5016B | 24 | G2 | AS | | 23-0 | 31-31-41 | D41091P | 17 | | | D41309P | 50 | | | 001-099 |
| 5016B | 24 | G2 | AS | | 23-0 | 31-31-21 | D41091P | 17 | | | D41309P | 50 | | | 115-199 |
| 5016R | 24 | G2 | AS | | 0-0 | 31-31-41 | D41091P | 16 | | | D41309P | 49 | | | 001-099 |
| 5016R | 24 | G2 | AS | | 0-0 | 31-31-21 | D41091P | 16 | | | D41309P | 49 | | | 115-199 |
| 5016Z | | | AS | | 0-0 | 31-31-41 | D41091P | 18 | | | D41309P | 51 | | | 001-099 |
| 5016Z | | | AS | | 0-0 | 31-31-21 | D41091P | 18 | | | D41309P | 51 | | | 115-199 |
| 5017B | 24 | G2 | AT | | 19-0 | 22-12-11 | D41091P | 20 | | | D41325P | 12 | | | ALL |
| 5017R | 24 | G2 | AT | | 0-0 | 22-12-11 | D41091P | 19 | | | D41325P | 11 | | | ALL |
| 5017Z | | | AT | | 0-0 | 22-12-11 | D41091P | 21 | | | D41325P | 13 | | | ALL |
| 5018B | 24 | G2 | AU | | 10-0 | 22-15-11 | D41097P | 2 | | | D41091P | 30 | | | ALL |
| 5018R | 24 | G2 | AU | | 0-0 | 22-15-11 | D41097P | 1 | | | D41091P | 29 | | | ALL |
| 5018Z | | | AU | | 0-0 | 22-15-11 | D41097P | 3 | | | D41091P | 31 | | | ALL |
| 5019B | 24 | G2 | AV | | 20-0 | 22-22-11 | D41091P | 33 | | | D41301P | 6 | | | ALL |
| 5019R | 24 | G2 | AV | | 0-0 | 22-22-11 | D41091P | 32 | | | D41301P | 5 | | | ALL |
| 5019Z | | | AV | | 0-0 | 22-22-11 | D41091P | 34 | | | D41301P | 7 | | | ALL |
| 5020B | 24 | G2 | AW | | 20-0 | SPARE | D41093P | 13 | | | D41325P | 15 | | | 115-199 |
| 5020R | 24 | G2 | AW | | 0-0 | SPARE | D41093P | 11 | | | D41325P | 16 | | | 115-199 |
| 5020Z | | | AW | | 0-0 | SPARE | D41093P | 12 | | | D41325P | 17 | | | 115-199 |
| 5021B | 24 | G2 | BD | | 20-0 | 22-24-11 | D41091P | 38 | | | D41301P | 17 | | | ALL |
| 5021R | 24 | G2 | BD | | 0-0 | 22-24-11 | D41091P | 37 | | | D41301P | 16 | | | ALL |
| 5021Z | | | BD | | 0-0 | 22-24-11 | D41091P | 39 | | | D41301P | 18 | | | ALL |
| 5022B | 24 | G2 | BE | | 21-0 | 22-32-12 | D41317P | 28 | | | D41097P | 5 | | | ALL |
| 5022R | 24 | G2 | BE | | 0-0 | 22-32-12 | D41317P | 27 | | | D41097P | 4 | | | ALL |
| 5022Z | | | BE | | 0-0 | 22-32-12 | D41317P | 29 | | | D41097P | 6 | | | ALL |
| 5023B | 24 | G2 | BF | | 23-0 | 22-41-11 | D41097P | 24 | | | D41303P | 9 | | | ALL |
| 5023R | 24 | G2 | BF | | 0-0 | 22-41-11 | D41097P | 23 | | | D41303P | 8 | | | ALL |
| 5023Z | | | BF | | 0-0 | 22-41-11 | D41097P | 25 | | | D41303P | 10 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 13

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 5024B | 24 | | G2 | BG | 22-0 | 22-41-11 | D41091P | | 41 | | D41303P | 12 | | | ALL |
| 5024R | 24 | | G2 | BG | 0-0 | 22-41-11 | D41091P | | 40 | | D41303P | 11 | | | ALL |
| 5024Z | | | | BG | 0-0 | 22-41-11 | D41091P | | 42 | | D41303P | 13 | | | ALL |
| 5025B | 24 | | G2 | BH | 22-0 | 22-41-11 | D41091P | | 47 | | D41303P | 18 | | | ALL |
| 5025R | 24 | | G2 | BH | 0-0 | 22-41-11 | D41091P | | 46 | | D41303P | 17 | | | ALL |
| 5025Z | | | | BH | 0-0 | 22-41-11 | D41091P | | 45 | | D41303P | 16 | | | ALL |
| 5026B | 24 | | G2 | BI | 24-0 | 22-41-12 | D41095P | | 2 | | D41303P | 20 | | | ALL |
| 5026R | 24 | | G2 | BI | 0-0 | 22-41-12 | D41095P | | 3 | | D41303P | 19 | | | ALL |
| 5026Z | | | | BI | 0-0 | 22-41-12 | D41095P | | 4 | | D41303P | 21 | | | ALL |
| 5027B | 24 | | G2 | BJ | 23-0 | 22-41-12 | D41097P | | 27 | | D41303P | 23 | | | ALL |
| 5027R | 24 | | G2 | BJ | 0-0 | 22-41-12 | D41097P | | 26 | | D41303P | 22 | | | ALL |
| 5027Z | | | | BJ | 0-0 | 22-41-12 | D41097P | | 28 | | D41303P | 24 | | | ALL |
| 5028B | 24 | | G2 | BK | 23-0 | 22-41-12 | D41097P | | 30 | | D41303P | 26 | | | ALL |
| 5028R | 24 | | G2 | BK | 0-0 | 22-41-12 | D41097P | | 29 | | D41303P | 25 | | | ALL |
| 5028Z | | | | BK | 0-0 | 22-41-12 | D41097P | | 31 | | D41303P | 27 | | | ALL |
| 5029B | 24 | | G2 | BL | 22-0 | 22-41-12 | D41093P | | 2 | | D41303P | 29 | | | ALL |
| 5029R | 24 | | G2 | BL | 0-0 | 22-41-12 | D41093P | | 1 | | D41303P | 28 | | | ALL |
| 5029Z | | | | BL | 0-0 | 22-41-12 | D41093P | | 3 | | D41303P | 30 | | | ALL |
| 5030B | 24 | | G2 | BM | 25-0 | 22-41-13 | D41317P | | 32 | | D41303P | 32 | | | ALL |
| 5030R | 24 | | G2 | BM | 0-0 | 22-41-13 | D41317P | | 31 | | D41303P | 31 | | | ALL |
| 5030Z | | | | BM | 0-0 | 22-41-13 | D41317P | | 33 | | D41303P | 33 | | | ALL |
| 5031B | 24 | | G2 | BN | 24-0 | 22-21-11 | D41099P | | 3 | | D41301P | 20 | | | ALL |
| 5031R | 24 | | G2 | BN | 0-0 | 22-21-11 | D41099P | | 2 | | D41301P | 19 | | | ALL |
| 5031Z | | | | BN | 0-0 | 22-21-11 | D41099P | | 1 | | D41301P | 21 | | | ALL |
| 5032B | 24 | | G2 | BO | 24-0 | SPARE | D41309P | | 31 | | D41317P | 35 | | | 001-099 |
| 5032R | 24 | | G2 | BO | 25-0 | 31-31-22 | D41309P | | 31 | | D41317P | 35 | | | 115-199 |
| 5032R | 24 | | G2 | BO | 0-0 | SPARE | D41309P | | 32 | | D41317P | 36 | | | 001-099 |
| 5032R | 24 | | G2 | BO | 0-0 | 31-31-22 | D41309P | | 32 | | D41317P | 36 | | | 115-199 |
| 5032Z | | | | BO | 0-0 | SPARE | D41309P | | 33 | | D41317P | 37 | | | 001-099 |
| 5032Z | | | | BO | 0-0 | 31-31-22 | D41309P | | 33 | | D41317P | 37 | | | 115-199 |
| 5034B | 24 | | G2 | BR | 23-0 | SPARE | D41317P | | 42 | | D41477P | 39 | | | 115-199 |
| 5034R | 24 | | G2 | BR | 0-0 | SPARE | D41317P | | 41 | | D41477P | 38 | | | 115-199 |
| 5034Z | | | | BR | 0-0 | SPARE | D41317P | | 43 | | D41477P | 40 | | | 115-199 |
| 5035B | 24 | | G2 | AZ | 16-0 | 31-51-21 | D41093P | | 44 | | D41481P | 38 | | | ALL |
| 5035R | 24 | | G2 | AZ | 0-0 | 31-51-21 | D41093P | | 45 | | D41481P | 37 | | | ALL |
| 5035Z | | | | AZ | 0-0 | 31-51-21 | D41093P | | 51 | | D41481P | 39 | | | ALL |
| 5036B | 24 | | G2 | BV | 19-0 | 34-12-12 | D41325P | | 43 | | D41091P | 52 | | | ALL |
| 5036R | 24 | | G2 | BV | 0-0 | 34-12-12 | D41325P | | 42 | | D41091P | 51 | | | ALL |
| 5036Z | | | | BV | 0-0 | 34-12-12 | D41325P | | 44 | | D41091P | 53 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 14

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-------------|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | |
| 5038B | 24 | G2 | BY | | 21-0 | 34-55-11 | D41093P | 20 | | | D41309P | 43 | | | ALL |
| 5038R | 24 | G2 | BY | | 0-0 | 34-55-11 | D41093P | 19 | | | D41309P | 42 | | | ALL |
| 5038Z | | | BY | | 0-0 | 34-55-11 | D41093P | 21 | | | D41309P | 44 | | | ALL |
| 5039B | 22 | GU | BZ | | 19-0 | 32-42-11 | D41099P | 9 | | | D41473P | 43 | | | 001-099 |
| 5039B | 24 | G2 | BZ | | 19-0 | 32-42-11 | D41099P | 9 | | | D41473P | 43 | | | 115-199 |
| 5039R | 22 | GU | BZ | | 0-0 | 32-42-11 | D41099P | 10 | | | D41473P | 44 | | | 001-099 |
| 5039R | 24 | G2 | BZ | | 0-0 | 32-42-11 | D41099P | 10 | | | D41473P | 44 | | | 115-199 |
| 5039Z | | | BZ | | 0-0 | 32-42-11 | D41099P | 11 | | | D41473P | 45 | | | ALL |
| 5040B | 24 | G2 | CA | | 10-0 | 34-25-11 | D41097P | 40 | | | D41093P | 30 | | | 001, 003-099, 115-199 |
| 5040B | 24 | G2 | CA | | 10-0 | SPARE | D41097P | 40 | | | D41093P | 30 | | | 002 |
| 5040R | 24 | G2 | CA | | 0-0 | 34-25-11 | D41097P | 39 | | | D41093P | 29 | | | 001, 003-099, 115-199 |
| 5040R | 24 | G2 | CA | | 0-0 | SPARE | D41097P | 39 | | | D41093P | 29 | | | 002 |
| 5040Z | | | CA | | 0-0 | 34-25-11 | D41097P | 38 | | | D41093P | 28 | | | 001, 003-099, 115-199 |
| 5040Z | | | CA | | 0-0 | SPARE | D41097P | 38 | | | D41093P | 28 | | | 002 |
| 5041B | 24 | G2 | CB | | 22-0 | 34-25-11 | D41097P | 43 | | | D41879P | 8 | | | 001, 003-099 |
| 5041B | 24 | G2 | CB | | 22-0 | SPARE | D41097P | 43 | | | D41879P | 8 | | | 002 |
| 5041B | 24 | G2 | CB | | 21-0 | 34-25-11 | D41097P | 43 | | | D41879P | 8 | | | 115-199 |
| 5041R | 24 | G2 | CB | | 0-0 | 34-25-11 | D41097P | 42 | | | D41879P | 7 | | | 001, 003-099, 115-199 |
| 5041R | 24 | G2 | CB | | 0-0 | SPARE | D41097P | 42 | | | D41879P | 7 | | | 002 |
| 5041Z | | | CB | | 0-0 | 34-25-11 | D41097P | 41 | | | D41879P | 6 | | | 001, 003-099, 115-199 |
| 5041Z | | | CB | | 0-0 | SPARE | D41097P | 41 | | | D41879P | 6 | | | 002 |
| 5042B | 24 | G2 | CC | | 20-0 | SPARE | D41089P | 41 | | | D41317P | 25 | | | 001-099 |
| 5042R | 24 | G2 | CC | | 0-0 | SPARE | D41089P | 40 | | | D41317P | 24 | | | 001-099 |
| 5042Z | | | CC | | 0-0 | SPARE | D41089P | DED | | | D41317P | 26 | | | 001-099 |
| 5044B | 24 | G2 | CE | | 24-0 | 31-31-43 | D43003P | 32 | | | D41307P | 36 | | | 001-099 |
| 5044B | 24 | G2 | CE | | 20-0 | SPARE | D41093P | 36 | | | D41325P | 52 | | | 115-199 |
| 5044R | 24 | G2 | CE | | 0-0 | 31-31-43 | D43003P | 31 | | | D41307P | 35 | | | 001-099 |
| 5044R | 24 | G2 | CE | | 0-0 | SPARE | D41093P | 35 | | | D41325P | 51 | | | 115-199 |
| 5044Z | | | CE | | 0-0 | 31-31-43 | D43003P | 33 | | | D41307P | 37 | | | 001-099 |
| 5044Z | | | CE | | 0-0 | SPARE | D41093P | 37 | | | D41325P | 53 | | | 115-199 |
| 5045B | 24 | G2 | CF | | 24-0 | SPARE | D41095P | 13 | | | D41303P | 39 | | | ALL |
| 5045R | 24 | G2 | CF | | 0-0 | SPARE | D41095P | 12 | | | D41303P | 38 | | | ALL |
| 5045Z | | | CF | | 0-0 | SPARE | D41095P | 14 | | | D41303P | 40 | | | ALL |
| 5047B | 24 | G2 | CH | | 24-0 | SPARE | D41099P | 24 | | | D41301P | 32 | | | ALL |
| 5047R | 24 | G2 | CH | | 0-0 | SPARE | D41099P | 23 | | | D41301P | 31 | | | ALL |
| 5047Z | | | CH | | 0-0 | SPARE | D41099P | 25 | | | D41301P | 33 | | | ALL |
| 5048B | 24 | G2 | CI | | 19-0 | SPARE | D41099P | 28 | | | D41473P | 49 | | | 001-099 |
| 5048B | 24 | G2 | CI | | 19-0 | SPARE | D41099P | 28 | | | D41473P | 27 | | | 115-199 |
| 5048R | 24 | G2 | CI | | 0-0 | SPARE | D41099P | 27 | | | D41473P | 48 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 15

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|-------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 5048R | 24 | G2 | CI | 0-0 | SPARE | D41099P | 27 | | | | D41473P | 14 | | | 115-199 |
| 5048Z | | | CI | 0-0 | SPARE | D41099P | 29 | | | | D41473P | 50 | | | 001-099 |
| 5048Z | | | CI | 0-0 | SPARE | D41099P | 29 | | | | D41473P | 33 | | | 115-199 |
| 5049B | 24 | G2 | CJ | 21-0 | SPARE | D41309P | CAP | Y | | | D41093P | 32 | | | 001-099 |
| 5049R | 24 | G2 | CJ | 0-0 | SPARE | D41309P | CAP | Y | | | D41093P | 31 | | | 001-099 |
| 5049Z | | | CJ | 0-0 | SPARE | D41309P | DED | | | | D41093P | 33 | | | 001-099 |
| 5050B | 24 | G2 | CK | 22-0 | 31-31-42 | D41093P | 47 | | | | D41309P | 54 | | | 001-099 |
| 5050B | 24 | G2 | CK | 21-0 | 31-31-22 | D41093P | 47 | | | | D41309P | 54 | | | 115-199 |
| 5050R | 24 | G2 | CK | 0-0 | 31-31-42 | D41093P | 46 | | | | D41309P | 53 | | | 001-099 |
| 5050R | 24 | G2 | CK | 0-0 | 31-31-22 | D41093P | 46 | | | | D41309P | 53 | | | 115-199 |
| 5050Z | | | CK | 0-0 | 31-31-42 | D41093P | 48 | | | | D41309P | 55 | | | 001-099 |
| 5050Z | | | CK | 0-0 | 31-31-22 | D41093P | 48 | | | | D41309P | 55 | | | 115-199 |
| 5051B | 24 | G2 | CM | 23-0 | 31-31-22 | D41093P | 32 | | | | D41307P | 2 | | | 115-199 |
| 5051R | 24 | G2 | CM | 0-0 | 31-31-22 | D41093P | 31 | | | | D41307P | 1 | | | 115-199 |
| 5051Z | | | CM | 0-0 | 31-31-22 | D41093P | 33 | | | | D41307P | 3 | | | 115-199 |
| 5052B | 24 | G2 | CN | 23-0 | 31-31-22 | D41093P | 54 | | | | D41307P | 6 | | | 115-199 |
| 5052R | 24 | G2 | CN | 0-0 | 31-31-22 | D41093P | 53 | | | | D41307P | 5 | | | 115-199 |
| 5052Z | | | CN | 0-0 | 31-31-22 | D41093P | 52 | | | | D41307P | 4 | | | 115-199 |
| 5053B | 24 | G2 | LA | 24-0 | 31-31-43 | D41307P | 7 | | | | D43003P | 26 | | | 001-099 |
| 5053B | 24 | G2 | CO | 23-0 | 31-31-22 | D41307P | 8 | | | | D41905P | 11 | | | 115-199 |
| 5053R | 24 | G2 | LA | 0-0 | 31-31-43 | D41307P | 6 | | | | D43003P | 25 | | | 001-099 |
| 5053R | 24 | G2 | CO | 0-0 | 31-31-22 | D41307P | 7 | | | | D41905P | 10 | | | 115-199 |
| 5053Z | | | LA | 0-0 | 31-31-43 | D41307P | 9 | | | | D43003P | 27 | | | 001-099 |
| 5053Z | | | CO | 0-0 | 31-31-22 | D41307P | 9 | | | | D41905P | 12 | | | 115-199 |
| 5054B | 24 | G2 | CP | 10-0 | 34-22-91 | D41097P | 54 | | | | D41099P | 34 | | | 001-099 |
| 5054B | 24 | G2 | CP | 10-0 | 34-22-93 | D41097P | 54 | | | | D41099P | 34 | | | 115-199 |
| 5054R | 24 | G2 | CP | 0-0 | 34-22-91 | D41097P | 53 | | | | D41099P | 33 | | | 001-099 |
| 5054R | 24 | G2 | CP | 0-0 | 34-22-93 | D41097P | 53 | | | | D41099P | 33 | | | 115-199 |
| 5054Z | | | CP | 0-0 | 34-22-91 | D41097P | 55 | | | | D41099P | 35 | | | 001-099 |
| 5054Z | | | CP | 0-0 | 34-22-93 | D41097P | 55 | | | | D41099P | 35 | | | 115-199 |
| 5055B | 24 | G2 | CQ | 8-0 | 21-31-21 | D42187P | 11 | | | | D41327P | 2 | | | ALL |
| 5055R | 24 | G2 | CQ | 0-0 | 21-31-21 | D42187P | 10 | | | | D41327P | 1 | | | ALL |
| 5055Z | | | CQ | 0-0 | 21-31-21 | D42187P | 12 | | | | D41327P | 3 | | | ALL |
| 5056B | 20 | QJ | LC | 10-0 | 31-31-44 | D41307P | 22 | | | | D41311P | 28 | | | 001-099 |
| 5056B | 24 | G2 | CV | 10-0 | 31-31-23 | D41307P | 22 | | | | D41311P | 28 | | | 115-199 |
| 5056R | 20 | QJ | LC | 0-0 | 31-31-44 | D41307P | 21 | | | | D41311P | 27 | | | 001-099 |
| 5056R | 24 | G2 | CV | 0-0 | 31-31-23 | D41307P | 21 | | | | D41311P | 27 | | | 115-199 |
| 5056Z | | | LC | 0-0 | 31-31-44 | D41307P | 23 | | | | D41311P | 29 | | | 001-099 |
| 5056Z | | | CV | 0-0 | 31-31-23 | D41307P | 23 | | | | D41311P | 29 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 16

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----------|-------|-------------|-------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | |
| 5061B | 24 | | G2 | DC | 16-0 | 34-16-11 | D41905P | 8 | | | D41481P | 31 | | | 001-099 |
| 5061B | 24 | | G2 | BA | 16-0 | 34-16-11 | D41905P | 8 | | | D41481P | 31 | | | 115-199 |
| 5061R | 24 | | G2 | DC | 0-0 | 34-16-11 | D41905P | 7 | | | D41481P | 30 | | | 001-099 |
| 5061R | 24 | | G2 | BA | 0-0 | 34-16-11 | D41905P | 7 | | | D41481P | 30 | | | 115-199 |
| 5061Z | | | | DC | 0-0 | 34-16-11 | D41905P | 9 | | | D41481P | 32 | | | 001-099 |
| 5061Z | | | | BA | 0-0 | 34-16-11 | D41905P | 9 | | | D41481P | 32 | | | 115-199 |
| 5062B | 24 | | G2 | DD | 9-0 | 24-22-12 | D42187P | 23 | | | D41329P | 17 | | | ALL |
| 5062R | 24 | | G2 | DD | 0-0 | 24-22-12 | D42187P | 24 | | | D41329P | 18 | | | ALL |
| 5062Z | | | | DD | 0-0 | 24-22-12 | D42187P | 25 | | | D41329P | 19 | | | ALL |
| 5063B | 24 | | G2 | DE | 16-0 | 31-51-34 | D41905P | 49 | | | D41481P | 34 | | | 009 |
| 5063B | 24 | | G2 | DE | 16-0 | 31-51-34 | D41905P | 15 | | | D41481P | 34 | | | 115-199 |
| 5063R | 24 | | G2 | DE | 0-0 | 31-51-34 | D41905P | 48 | | | D41481P | 33 | | | 009 |
| 5063R | 24 | | G2 | DE | 0-0 | 31-51-34 | D41905P | 14 | | | D41481P | 33 | | | 115-199 |
| 5063Z | | | | DE | 0-0 | 31-51-34 | D41905P | 46 | | | D41481P | 35 | | | 009 |
| 5063Z | | | | DE | 0-0 | 31-51-34 | D41905P | 16 | | | D41481P | 35 | | | 115-199 |
| 5064B | 24 | | G2 | DG | 9-0 | 22-12-31 | D41643P | 8 | | | D41905P | 31 | | | ALL |
| 5064R | 24 | | G2 | DG | 0-0 | 22-12-31 | D41643P | 7 | | | D41905P | 30 | | | ALL |
| 5064Z | | | | DG | 0-0 | 22-12-31 | D41643P | 9 | | | D41905P | 32 | | | ALL |
| 5065B | 24 | | G2 | DH | 24-0 | 22-21-21 | D41099P | 5 | | | D40015P | 5 | | | ALL |
| 5065R | 24 | | G2 | DH | 0-0 | 22-21-21 | D41099P | 6 | | | D40015P | 4 | | | ALL |
| 5065Z | | | | DH | 0-0 | 22-21-21 | D41099P | 7 | | | D40015P | 6 | | | ALL |
| 5066B | 24 | | G2 | BA | 20-0 | 22-24-21 | D41905P | 26 | | | D40015P | 2 | | | 001-099 |
| 5066B | 24 | | G2 | BU | 20-0 | 22-24-21 | D41905P | 26 | | | D40015P | 2 | | | 115-199 |
| 5066R | 24 | | G2 | BA | 0-0 | 22-24-21 | D41905P | 25 | | | D40015P | 1 | | | 001-099 |
| 5066R | 24 | | G2 | BU | 0-0 | 22-24-21 | D41905P | 25 | | | D40015P | 1 | | | 115-199 |
| 5066Z | | | | BA | 0-0 | 22-24-21 | D41905P | 27 | | | D40015P | 3 | | | 001-099 |
| 5066Z | | | | BU | 0-0 | 22-24-21 | D41905P | 27 | | | D40015P | 3 | | | 115-199 |
| 5067B | 24 | | G2 | BB | 12-0 | 34-21-11 | D41099P | 38 | | | D41095P | 38 | | | ALL |
| 5067R | 24 | | G2 | BB | 0-0 | 34-21-11 | D41099P | 37 | | | D41095P | 37 | | | ALL |
| 5067Z | | | | BB | 0-0 | 34-21-11 | D41099P | 39 | | | D41095P | 39 | | | ALL |
| 5068B | 24 | | G2 | BX | 10-0 | 22-33-11 | D41643P | 12 | | | D41905P | 34 | | | 001-099 |
| 5068B | 24 | | G2 | BX | 9-0 | 22-33-11 | D41643P | 12 | | | D41905P | 34 | | | 115-199 |
| 5068R | 24 | | G2 | BX | 0-0 | 22-33-11 | D41643P | 11 | | | D41905P | 33 | | | ALL |
| 5068Z | | | | BX | 0-0 | 22-33-11 | D41643P | 13 | | | D41905P | 35 | | | ALL |
| 5069B | 24 | | G2 | DI | 15-0 | 34-61-15 | D41475P | 24 | | | D41905P | 40 | | | ALL |
| 5069R | 24 | | G2 | DI | 0-0 | 34-61-15 | D41475P | 23 | | | D41905P | 39 | | | ALL |
| 5069Z | | | | DI | 0-0 | 34-61-15 | D41475P | 25 | | | D41905P | 41 | | | ALL |
| 5070B | 24 | | G2 | DJ | 15-0 | 34-61-15 | D41475P | 26 | | | D41905P | 42 | | | ALL |
| 5070R | 24 | | G2 | DJ | 0-0 | 34-61-15 | D41475P | 27 | | | D41905P | 43 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 17

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|-------------------------------------|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 5070Z | | | | DJ | 0-0 | 34-61-15 | | D41475P | 28 | | | D41905P | 44 | | | ALL |
| 5071B | 24 | G2 | | DK | 17-0 | 34-61-15 | | D41475P | 30 | | | D41095P | 18 | | | ALL |
| 5071R | 24 | G2 | | DK | 0-0 | 34-61-15 | | D41475P | 29 | | | D41095P | 17 | | | ALL |
| 5071Z | | | | DK | 0-0 | 34-61-15 | | D41475P | 31 | | | D41095P | 19 | | | ALL |
| 5072B | 24 | G2 | | DL | 20-0 | 22-33-11 | | D41643P | 15 | | | D41879P | 47 | | | 001-099 |
| 5072B | 24 | G2 | | DN | 20-0 | 22-33-11 | | D41643P | 15 | | | D41879P | 47 | | | 115-199 |
| 5072R | 24 | G2 | | DL | 0-0 | 22-33-11 | | D41643P | 14 | | | D41879P | 46 | | | 001-099 |
| 5072R | 24 | G2 | | DN | 0-0 | 22-33-11 | | D41643P | 14 | | | D41879P | 46 | | | 115-199 |
| 5072Z | | | | DL | 0-0 | 22-33-11 | | D41643P | 16 | | | D41879P | 45 | | | 001-099 |
| 5072Z | | | | DN | 0-0 | 22-33-11 | | D41643P | 16 | | | D41879P | 45 | | | 115-199 |
| 5074B | 24 | G2 | | CD | 24-0 | SPARE | | D41099P | 19 | | | D40015P | 8 | | | 001-099 |
| 5074R | 24 | G2 | | CD | 0-0 | SPARE | | D41099P | 18 | | | D40015P | 7 | | | 001-099 |
| 5074Z | | | | CD | 0-0 | SPARE | | D41099P | 20 | | | D40015P | 9 | | | 001-099 |
| 5078B | 22 | GU | | DO | 11-0 | 34-58-11 | | D41643P | 5 | | | D41099P | 40 | | | 115-199 |
| 5078R | 22 | GU | | DO | 0-0 | 34-58-11 | | D41643P | 4 | | | D41099P | 36 | | | 115-199 |
| 5078Z | | | | DO | 0-0 | 34-58-11 | | D41643P | 24 | | | D41099P | 41 | | | 115-199 |
| 5079B | 24 | G2 | | KT | 16-0 | 27-32-11 | | D41905P | 51 | | | D41481P | 51 | | | 001-099 |
| 5079R | 24 | G2 | | KT | 0-0 | 27-32-11 | | D41905P | 50 | | | D41481P | 50 | | | 001-099 |
| 5079Z | | | | KT | 0-0 | 27-32-11 | | D41905P | 52 | | | D41481P | 52 | | | 001-099 |
| 5080B | 24 | G2 | | KA | 21-0 | 34-22-19 | | D41089P | 54 | | | D43001P | 2 | | | 001-099 |
| 5080R | 24 | G2 | | KA | 0-0 | 34-22-19 | | D41089P | 53 | | | D43001P | 1 | | | 001-099 |
| 5080Z | | | | KA | 0-0 | 34-22-19 | | D41089P | 55 | | | D43001P | 3 | | | 001-099 |
| 5081B | 24 | G2 | | KB | 20-0 | 34-51-11 | | D43003P | 6 | | | D43001P | 6 | | | 001-099 |
| 5081R | 24 | G2 | | KB | 0-0 | 34-51-11 | | D43003P | 5 | | | D43001P | 5 | | | 001-099 |
| 5081Z | | | | KB | 0-0 | 34-51-11 | | D43003P | 7 | | | D43001P | 7 | | | 001-099 |
| 5082B | 24 | G2 | | KC | 20-0 | 34-51-11 | | D43003P | 9 | | | D43001P | 9 | | | 001-099 |
| 5082R | 24 | G2 | | KC | 0-0 | 34-51-11 | | D43003P | 8 | | | D43001P | 8 | | | 001-099 |
| 5082Z | | | | KC | 0-0 | 34-51-11 | | D43003P | 10 | | | D43001P | 10 | | | 001-099 |
| 5083B | 24 | G2 | | KD | 27-0 | 23-51-13 | | D41319P | 26 | | | D43001P | 13 | | | 001-099 |
| 5083R | 24 | G2 | | KD | 0-0 | 23-51-13 | | D41319P | 25 | | | D43001P | 12 | | | 001-099 |
| 5083Z | | | | KD | 0-0 | 23-51-13 | | D41319P | 27 | | | D43001P | 14 | | | 001-099 |
| 5086B | 24 | G2 | | KG | 28-0 | 23-51-12 | | D41319P | 52 | | | D41303P | 52 | | | 001-099 |
| 5086R | 24 | G2 | | KG | 0-0 | 23-51-12 | | D41319P | 51 | | | D41303P | 51 | | | 001-099 |
| 5086Z | | | | KG | 0-0 | 23-51-12 | | D41319P | 53 | | | D41303P | 53 | | | 001-099 |
| 5087B | 24 | G2 | | KH | 28-0 | 23-51-12 | | D41319P | 29 | | | D41303P | 49 | | | 001-099 |
| 5087R | 24 | G2 | | KH | 0-0 | 23-51-12 | | D41319P | 28 | | | D41303P | 48 | | | 001-099 |
| 5087Z | | | | KH | 0-0 | 23-51-12 | | D41319P | 30 | | | D41303P | 50 | | | 001-099 |
| 5088B | 24 | G2 | | KI | 20-0 | SPARE | | D43003P | 13 | | | D43001P | 18 | | | 001-099 |
| 5088R | 24 | G2 | | KI | 0-0 | SPARE | | D43003P | 12 | | | D43001P | 17 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 18

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|-------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 5088Z | | | | KI | 0-0 | SPARE | D43003P | 14 | | | D43001P | 19 | | | 001-099 |
| 5090B | 24 | G2 | | KS | 9-0 | 22-13-11 | D41905P | 2 | | | D41643P | 34 | | | 001-099 |
| 5090B | 24 | G2 | | KS | 8-0 | 22-13-11 | D43003P | 44 | | | D41643P | 34 | | | 115-199 |
| 5090R | 24 | G2 | | KS | 0-0 | 22-13-11 | D41905P | 1 | | | D41643P | 33 | | | 001-099 |
| 5090R | 24 | G2 | | KS | 0-0 | 22-13-11 | D43003P | 43 | | | D41643P | 33 | | | 115-199 |
| 5090Z | | | | KS | 0-0 | 22-13-11 | D41905P | 3 | | | D41643P | 35 | | | 001-099 |
| 5090Z | | | | KS | 0-0 | 22-13-11 | D43003P | 45 | | | D41643P | 35 | | | 115-199 |
| 5091B | 24 | G2 | | KL | 17-0 | 34-46-12 | D41097P | 45 | | | D41481P | 45 | | | ALL |
| 5091R | 24 | G2 | | KL | 0-0 | 34-46-12 | D41097P | 44 | | | D41481P | 44 | | | ALL |
| 5091Z | | | | KL | 0-0 | 34-46-12 | D41097P | 46 | | | D41481P | 46 | | | ALL |
| 5092B | 24 | G2 | | KM | 25-0 | 27-32-11 | D41327P | 14 | | | D41481P | 54 | | | 001-099 |
| 5092B | 24 | G2 | | KM | 19-0 | 27-32-11 | D41475P | 54 | | | D41481P | 54 | | | 115-199 |
| 5092R | 24 | G2 | | KM | 0-0 | 27-32-11 | D41327P | 13 | | | D41481P | 53 | | | 001-099 |
| 5092R | 24 | G2 | | KM | 0-0 | 27-32-11 | D41475P | 53 | | | D41481P | 53 | | | 115-199 |
| 5092Z | | | | KM | 0-0 | 27-32-11 | D41327P | 15 | | | D41481P | 55 | | | 001-099 |
| 5092Z | | | | KM | 0-0 | 27-32-11 | D41475P | 55 | | | D41481P | 55 | | | 115-199 |
| 5093B | 24 | G2 | | KN | 10-0 | 34-22-29 | D41097P | 33 | | | D41095P | 23 | | | 001-099 |
| 5093B | 24 | G2 | | KN | 10-0 | 34-22-29 | D41097P | 33 | | | D41095P | 42 | | | 115-199 |
| 5093R | 24 | G2 | | KN | 0-0 | 34-22-29 | D41097P | 32 | | | D41095P | 41 | | | ALL |
| 5093Z | | | | KN | 0-0 | 34-22-29 | D41097P | 34 | | | D41095P | 40 | | | ALL |
| 5094B | 24 | G2 | | KO | 11-0 | 34-22-29 | D41093P | 54 | | | D41095P | 25 | | | 001-099 |
| 5094B | 24 | G2 | | KO | 11-0 | 34-22-29 | D41093P | 40 | | | D41095P | 54 | | | 115-199 |
| 5094R | 24 | G2 | | KO | 0-0 | 34-22-29 | D41093P | 53 | | | D41095P | 24 | | | 001-099 |
| 5094R | 24 | G2 | | KO | 0-0 | 34-22-29 | D41093P | 39 | | | D41095P | 53 | | | 115-199 |
| 5094Z | | | | KO | 0-0 | 34-22-29 | D41093P | 55 | | | D41095P | 26 | | | 001-099 |
| 5094Z | | | | KO | 0-0 | 34-22-29 | D41093P | 41 | | | D41095P | 55 | | | 115-199 |
| 5095B | 24 | G2 | | KP | 8-0 | 34-31-11 | D41643P | 37 | | | D43003P | 21 | | | ALL |
| 5095R | 24 | G2 | | KP | 0-0 | 34-31-11 | D41643P | 36 | | | D43003P | 20 | | | ALL |
| 5095Z | | | | KP | 0-0 | 34-31-11 | D41643P | 38 | | | D43003P | 22 | | | ALL |
| 5096B | 24 | G2 | | LD | 15-0 | 34-45-02 | D41473P | 49 | | | D43003P | 18 | | | 115-199 |
| 5096R | 24 | G2 | | LD | 0-0 | 34-45-02 | D41473P | 48 | | | D43003P | 17 | | | 115-199 |
| 5096Z | | | | LD | 0-0 | 34-45-02 | D41473P | 50 | | | D43003P | 19 | | | 115-199 |
| 5101B | 22 | X2 | | EP | 20-0 | 34-61-16 | D43023P | 4 | | | D43019P | 4 | | | 115-199 |
| 5101R | 22 | X2 | | EP | 0-0 | 34-61-16 | D43023P | 3 | | | D43019P | 3 | | | 115-199 |
| 5101Z | | | | EP | 0-0 | 34-61-16 | D43023P | 5 | | | D43019P | 5 | | | 115-199 |
| 5102B | 22 | X2 | | EQ | 20-0 | 34-61-16 | D43023P | 7 | | | D43019P | 7 | | | 115-199 |
| 5102R | 22 | X2 | | EQ | 0-0 | 34-61-16 | D43023P | 6 | | | D43019P | 6 | | | 115-199 |
| 5102Z | | | | EQ | 0-0 | 34-61-16 | D43023P | 8 | | | D43019P | 8 | | | 115-199 |
| 5103B | 22 | X2 | | ER | 20-0 | 34-61-16 | D43019P | 10 | | | D41095P | 46 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 19

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4471 | 286N4471 | | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | |
| 5103R | 22 | | X2 | ER | 0-0 | 34-61-16 | D43019P | | | | D41095P | 45 | | | 115-199 |
| 5103Z | | | | ER | 0-0 | 34-61-16 | D43019P | | | | D41095P | 47 | | | 115-199 |
| 5104B | 22 | | X2 | FD | 20-0 | 34-61-16 | D43019P | | | | D41095P | 52 | | | 115-199 |
| 5104R | 22 | | X2 | FD | 0-0 | 34-61-16 | D43019P | | | | D41095P | 51 | | | 115-199 |
| 5104Z | | | | FD | 0-0 | 34-61-16 | D43019P | | | | D41095P | 43 | | | 115-199 |
| 5105B | 22 | | X2 | FE | 20-0 | 34-61-16 | D43023P | | | | D43019P | 16 | | | 115-199 |
| 5105R | 22 | | X2 | FE | 0-0 | 34-61-16 | D43023P | | | | D43019P | 15 | | | 115-199 |
| 5105Z | | | | FE | 0-0 | 34-61-16 | D43023P | | | | D43019P | 17 | | | 115-199 |
| 5106B | 22 | | X2 | FF | 20-0 | 34-61-16 | D43023P | | | | D43019P | 21 | | | 115-199 |
| 5106R | 22 | | X2 | FF | 0-0 | 34-61-16 | D43023P | | | | D43019P | 20 | | | 115-199 |
| 5106Z | | | | FF | 0-0 | 34-61-16 | D43023P | | | | D43019P | 22 | | | 115-199 |
| 5111B | 22 | | X2 | FK | 15-7 | 34-22-38 | D41643P | | | | D41475P | 50 | | | 115-199 |
| 5111R | 22 | | X2 | FK | 0-0 | 34-22-38 | D41643P | | | | D41475P | 52 | | | 115-199 |
| 5111Z | | | | FK | 0-0 | 34-22-38 | D41643P | | | | D41475P | 51 | | | 115-199 |
| 5115B | 24 | | G2 | LB | 24-0 | 31-31-43 | D41307P | | | | D43003P | 29 | | | 001-099 |
| 5115R | 24 | | G2 | LB | 0-0 | 31-31-43 | D41307P | | | | D43003P | 28 | | | 001-099 |
| 5115Z | | | | LB | 0-0 | 31-31-43 | D41307P | | | | D43003P | 30 | | | 001-099 |
| 5117B | 22 | | X2 | FS | 16-8 | 34-22-38 | D43023P | | | | D43019P | 24 | | | 115-199 |
| 5117R | 22 | | X2 | FS | 0-0 | 34-22-38 | D43023P | | | | D43019P | 23 | | | 115-199 |
| 5117Z | | | | FS | 0-0 | 34-22-38 | D43023P | | | | D43019P | 25 | | | 115-199 |
| 5126B | 24 | | G2 | KF | 23-0 | 34-45-01 | D41093P | | | | D41307P | 42 | | | 001-099 |
| 5126B | 24 | | G2 | KF | 23-0 | 34-45-01 | D43003P | | | | D41307P | 42 | | | 115-199 |
| 5126R | 24 | | G2 | KF | 0-0 | 34-45-01 | D41093P | | | | D41307P | 41 | | | 001-099 |
| 5126R | 24 | | G2 | KF | 0-0 | 34-45-01 | D43003P | | | | D41307P | 41 | | | 115-199 |
| 5126Z | | | | KF | 0-0 | 34-45-01 | D41093P | | | | D41307P | 43 | | | 001-099 |
| 5126Z | | | | KF | 0-0 | 34-45-01 | D43003P | | | | D41307P | 43 | | | 115-199 |
| 5127B | 24 | | G2 | KE | 24-0 | 34-45-02 | D41307P | | | | D41905P | 17 | | | 001-099 |
| 5127B | 24 | | G2 | LE | 23-0 | 34-45-02 | D41307P | | | | D43003P | 35 | | | 115-199 |
| 5127R | 24 | | G2 | KE | 0-0 | 34-45-02 | D41307P | | | | D41905P | 16 | | | 001-099 |
| 5127R | 24 | | G2 | LE | 0-0 | 34-45-02 | D41307P | | | | D43003P | 34 | | | 115-199 |
| 5127Z | | | | KE | 0-0 | 34-45-02 | D41307P | | | | D41905P | 12 | | | 001-099 |
| 5127Z | | | | LE | 0-0 | 34-45-02 | D41307P | | | | D43003P | 36 | | | 115-199 |
| 5128B | 24 | | G2 | KK | 24-0 | 34-45-02 | D41307P | | | | D41905P | 54 | | | 001-099 |
| 5128B | 24 | | G2 | KK | 23-0 | 34-45-02 | D41307P | | | | D43003P | 38 | | | 115-199 |
| 5128R | 24 | | G2 | KK | 0-0 | 34-45-02 | D41307P | | | | D41905P | 53 | | | 001-099 |
| 5128R | 24 | | G2 | KK | 0-0 | 34-45-02 | D41307P | | | | D43003P | 37 | | | 115-199 |
| 5128Z | | | | KK | 0-0 | 34-45-02 | D41307P | | | | D41905P | 55 | | | 001-099 |
| 5128Z | | | | KK | 0-0 | 34-45-02 | D41307P | | | | D43003P | 39 | | | 115-199 |
| 5130B | 24 | | G2 | KR | 13-0 | 31-31-42 | D41093P | | | | D41637P | 14 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 20

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|------|-------------------------------------|---------|---------|------|------|--------|---------|------|------|--------|------------------|-------------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4471 | 286N4471 | | | | E/E RACK,INTERRACK LEFT (continued) | | | | | | | | | | | |
| 5130R | 24 | G2 | KR | 0-0 | 31-31-42 | D41093P | 11 | | | | D41637P | 13 | | | 001-099 | |
| 5130Z | | | KR | 0-0 | 31-31-42 | D41093P | 13 | | | | D41637P | 15 | | | 001-099 | |
| 5136B | 22 | X2 | ES | 20-0 | 34-61-16 | D43019P | 45 | | | | D41095P | 49 | | | 115-199 | |
| 5136R | 22 | X2 | ES | 0-0 | 34-61-16 | D43019P | 44 | | | | D41095P | 48 | | | 115-199 | |
| 5136Z | | | ES | 0-0 | 34-61-16 | D43019P | 46 | | | | D41095P | 50 | | | 115-199 | |
| 5144B | 22 | GU | JM | 8-3 | 31-31-42 | D41311P | 20 | | | | D41307P | 25 | | | 010-099 | |
| 5144R | 22 | GU | JM | 0-0 | 31-31-42 | D41311P | 21 | | | | D41307P | 24 | | | 010-099 | |
| 5144Z | | | JM | 0-0 | 31-31-42 | D41311P | 22 | | | | D41307P | 26 | | | 010-099 | |
| 5228B | 22 | GU | AG | 40-0 | 34-43-14 | D00109 | 2 | | | | SP00487 | | 9 | | 002 | |
| 5228R | 22 | GU | AG | 0-0 | 34-43-14 | D00109 | 1 | | | | SP00485 | | 9 | | 002 | |
| 5228Z | | | AG | 0-0 | 34-43-14 | D00109 | DED | | | | SP00489 | | 9 | | 002 | |
| 5304B | 24 | G2 | KU | 24-0 | 31-31-43 | D43003P | 35 | | | | D41307P | 39 | | | 001-099 | |
| 5304R | 24 | G2 | KU | 0-0 | 31-31-43 | D43003P | 34 | | | | D41307P | 38 | | | 001-099 | |
| 5304Z | | | KU | 0-0 | 31-31-43 | D43003P | 36 | | | | D41307P | 40 | | | 001-099 | |
| 5305B | 24 | G2 | KZ | 24-0 | 31-31-43 | D43003P | 38 | | | | D41307P | 32 | | | 001-099 | |
| 5305R | 24 | G2 | KZ | 0-0 | 31-31-43 | D43003P | 37 | | | | D41307P | 31 | | | 001-099 | |
| 5305Z | | | KZ | 0-0 | 31-31-43 | D43003P | 39 | | | | D41307P | 33 | | | 001-099 | |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT | | | | | | | | | | | |
| 0001 | 22 | GA | | 17-0 | 34-61-15 | D41487P | 1 | | | | D41339P | 1 | | | 001-008, 115-199 | |
| 0001 | 22 | GA | | 17-0 | SPARE | D41487P | 1 | | | | D41339P | 1 | | | 009-099 | |
| 0002 | 24 | GK | | 17-0 | 34-61-24 | D41487P | 2 | | | | D41345P | 10 | | | ALL | |
| 0003 | 24 | GK | | 22-0 | 34-61-25 | D41369P | 17 | | | | D41345P | 17 | | | ALL | |
| 0004 | 22 | GA | | 22-0 | 34-21-21 | D41369P | 10 | | | | D41351P | 38 | | | ALL | |
| 0005 | 22 | GA | | 22-0 | 34-21-21 | D41369P | 11 | | | | D41351P | 39 | | | ALL | |
| 0006 | 22 | GA | | 22-0 | 34-21-21 | D41369P | 12 | | | | D41351P | 40 | | | ALL | |
| 0011 | 24 | GK | | 20-0 | 27-32-21 | D41487P | 6 | | | | D41491P | 4 | | | ALL | |
| 0012 | 24 | GK | | 20-0 | SPARE | D41487P | 7 | | | | D41491P | 12 | | | 001-099 | |
| 0012 | 24 | GK | | 20-0 | SPARE | D41487P | 7 | | | | D41491P | 5 | | | 115-199 | |
| 0013 | 24 | GK | | 23-0 | SPARE | D41367P | 1 | | | | D41491P | 6 | | | ALL | |
| 0014 | 22 | GA | | 23-0 | 27-32-21 | D41367P | 2 | | | | D41491P | 7 | | | 001-099 | |
| 0014 | 24 | GK | | 23-0 | 27-32-21 | D41367P | 2 | | | | D41491P | 7 | | | 115-199 | |
| 0016 | 24 | GK | | 17-0 | SPARE | D41349P | 30 | | | | D41487P | 49 | | | 001, 003-099 | |
| 0016 | 22 | GA | | 17-0 | SPARE | D41349P | REF | VP | | | D41487P | 49 | | | 002 | |
| 0017 | 24 | GK | | 25-0 | 27-32-21 | D41377P | 41 | | | | D41491P | 10 | | | 001-099 | |
| 0017 | 24 | GK | | 25-0 | 27-32-21 | D41379P | 8 | | | | D41491P | 10 | | | 115-199 | |
| 0018 | 24 | GK | | 25-0 | 27-32-21 | D41377P | 42 | | | | D41491P | 11 | | | ALL | |
| 0019 | 24 | GK | | 25-0 | SPARE | D41377P | 43 | | | | D41491P | 14 | | | 001-099 | |
| 0019 | 24 | GK | | 25-0 | 34-12-12 | D41379P | 10 | | | | D41491P | CAP | Y | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 21

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | | |
| 0020 | 24 | | GK | | 25-0 | SPARE | D41377P | 44 | | | | D41491P | 13 | | | 001-099 | |
| 0021 | 24 | | GK | | 25-0 | 27-32-21 | D41377P | 1 | | | | D41491P | 15 | | | ALL | |
| 0022 | 24 | | GK | | 25-0 | 27-32-21 | D41377P | 45 | | | | D41491P | 16 | | | 001-099 | |
| 0022 | 24 | | GK | | 25-0 | 27-32-21 | D41379P | 12 | | | | D41491P | 16 | | | 115-199 | |
| 0023 | 24 | | GK | | 25-0 | 31-51-33 | D41369P | 22 | | | | D41491P | 18 | | | ALL | |
| 0024 | 24 | | GK | | 25-0 | 31-51-41 | D41867P | 18 | | | | D41491P | 19 | | | ALL | |
| 0025 | 24 | | GK | | 23-0 | 31-51-42 | D41367P | 4 | | | | D41491P | 20 | | | ALL | |
| 0026 | 24 | | GK | | 26-0 | 23-12-21 | D41371P | 9 | | | | D41909P | 21 | | | 001-099 | |
| 0026 | 24 | | GK | | 26-0 | 23-12-21 | D41909P | 21 | | | | D41371P | 9 | | | 115-199 | |
| 0027 | 22 | | GA | | 22-0 | 27-51-51 | D41377P | 9 | | | | S10329 | 2 | C | | ALL | |
| 0028 | 20 | | GA | | 3-0 | 27-51-51 | S10329 | 1 | C | | | GD02243 | DC.. | E | | ALL | |
| 0029 | 24 | | GK | | 24-0 | SPARE | D41487P | 8 | | | | D41381P | 4 | | | 115-199 | |
| 0031 | 24 | | GK | | 18-0 | 31-51-21 | D41907P | 22 | | | | D41491P | 49 | | | ALL | |
| 0032 | 24 | | GK | | 22-0 | 34-12-22 | D41867P | 30 | | | | D41907P | 10 | | | 001-099 | |
| 0032 | 24 | | GK | | 22-0 | 34-12-22 | D41907P | 10 | | | | D41867P | 30 | | | 115-199 | |
| 0033 | 24 | | GK | | 23-0 | 24-28-11 | D41487P | 33 | | | | D41369P | 13 | | | ALL | |
| 0036 | 22 | | GA | | 10-0 | 27-09-13 | D41367P | 6 | | | | D41867P | 12 | | | ALL | |
| 0037 | 22 | | GA | | 22-0 | SPARE | D41367P | 47 | | | | D41487P | 10 | | | ALL | |
| 0038 | 24 | | GK | | 23-0 | SPARE | D41487P | 11 | | | | D41369P | 26 | | | 115-199 | |
| 0039 | 22 | | GA | | 22-0 | 27-09-12 | D41367P | 8 | | | | D41487P | 12 | | | 115-199 | |
| 0040 | 22 | | GA | | 10-0 | 22-21-21 | D41369P | 31 | | | | D41367P | 9 | | | ALL | |
| 0041 | 22 | | GA | | 20-0 | 22-21-21 | D41351P | 4 | | | | D41367P | 13 | | | ALL | |
| 0042 | 22 | | GA | | 20-0 | 22-22-21 | D41345P | 30 | | | | D41367P | 14 | | | ALL | |
| 0043 | 22 | | GA | | 20-0 | 22-22-21 | D41345P | 34 | | | | D41367P | 18 | | | ALL | |
| 0044 | 24 | | GK | | 18-0 | SPARE | D41369P | 32 | | | | D41379P | 22 | | | 115-199 | |
| 0045 | 24 | | GK | | 18-0 | SPARE | D41369P | 33 | | | | D41379P | 23 | | | 115-199 | |
| 0046 | 24 | | GK | | 22-0 | 34-61-26 | D41907P | 9 | | | | D41867P | 31 | | | 115-199 | |
| 0047 | 24 | | GK | | 22-0 | SPARE | D41867P | 32 | | | | D41907P | 12 | | | 001-099 | |
| 0047 | 24 | | GK | | 22-0 | SPARE | D41907P | 12 | | | | D41867P | 32 | | | 115-199 | |
| 0048 | 20 | | GA | | 24-0 | 35-11-13 | D41369P | 37 | | | | D02284 | 1 | | | 001-099 | |
| 0051 | 20 | | GA | | 13-0 | SPARE | D41487P | 13 | | | | D41489P | 9 | | | 115-199 | |
| 0052 | 24 | | GK | | 23-0 | SPARE | D41487P | 14 | | | | D41369P | 40 | | | ALL | |
| 0053 | 24 | | GK | | 10-0 | SPARE | D41367P | 3 | | | | D41369P | 41 | | | 001-099 | |
| 0053 | 24 | | GK | | 18-0 | SPARE | D41379P | 32 | | | | D41369P | 41 | | | 115-199 | |
| 0054 | 24 | | GK | | 13-0 | SPARE | D41489P | 10 | | | | D41487P | 15 | | | 115-199 | |
| 0055 | 22 | | GA | | 16-0 | 34-61-21 | D41487P | 16 | | | | D41347P | 30 | | | 001-099 | |
| 0055 | 24 | | GK | | 23-0 | SPARE | D41487P | 16 | | | | D41369P | 42 | | | 115-199 | |
| 0056 | 24 | | GK | | 7-0 | SPARE | D41377P | 19 | | | | D41379P | 33 | | | 001-099 | |
| 0056 | 24 | | GK | | 18-0 | SPARE | D41369P | 43 | | | | D41379P | 33 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 22

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-------------|-----------------|-------|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | |
| 0057 | 22 | GA | | | 20-0 | 22-12-21 | D41347P | | 1 | | D41379P | | 14 | | ALL |
| 0058 | 22 | GA | | | 20-0 | 22-12-21 | D41347P | | 2 | | D41379P | | 15 | | ALL |
| 0059 | 22 | GA | | | 19-0 | 22-12-21 | D41347P | | 3 | | D41489P | | 13 | | ALL |
| 0060 | 22 | GA | | | 19-0 | 22-12-21 | D41347P | | 4 | | D41489P | | 14 | | ALL |
| 0061 | 22 | GA | | | 20-0 | 22-12-21 | D41347P | | 8 | | D41379P | | 37 | | ALL |
| 0062 | 24 | GK | | | 23-0 | SPARE | D41867P | | 1 | | D41487P | | 17 | | 115-199 |
| 0063 | 24 | GK | | | 25-0 | SPARE | D41867P | | 2 | | D41491P | | 41 | | 001, 003-099 |
| 0063 | 24 | GK | | | 25-0 | SPARE | D41867P | REF | VP | | D41491P | | 41 | | 002 |
| 0063 | 24 | GK | | | 23-0 | SPARE | D41867P | | 2 | | D41487P | | 18 | | 115-199 |
| 0064 | 22 | GA | | | 16-0 | 30-32-11 | D41487P | | 19 | | D41347P | | 12 | | ALL |
| 0065 | 22 | GA | | | 16-0 | 30-32-11 | D41487P | | 20 | | D41347P | | 13 | | ALL |
| 0066 | 24 | GK | | | 25-0 | 34-55-21 | D41345P | | 51 | | D41355P | | 20 | | ALL |
| 0067 | 24 | GK | | | 17-0 | 34-55-21 | D41345P | | 52 | | D41487P | | 21 | | ALL |
| 0068 | 24 | GK | | | 16-0 | 34-12-22 | D41347P | | 14 | | D41487P | | 22 | | ALL |
| 0069 | 24 | GK | | | 16-0 | 34-12-22 | D41347P | | 15 | | D41487P | | 23 | | ALL |
| 0070 | 24 | GK | | | 16-0 | 34-12-22 | D41347P | | 16 | | D41487P | | 24 | | ALL |
| 0071 | 24 | GK | | | 16-0 | 34-12-22 | D41347P | | 17 | | D41487P | | 25 | | ALL |
| 0072 | 22 | GA | | | 20-0 | SPARE | D41347P | | 21 | | D41379P | | 38 | | 001-099 |
| 0072 | 24 | GK | | | 20-0 | SPARE | D41347P | | 21 | | D41379P | | 38 | | 115-199 |
| 0074 | 22 | GA | | | 16-0 | 34-12-21 | D41487P | | 26 | | D41347P | | 37 | | ALL |
| 0075 | 22 | GA | | | 16-0 | 34-12-21 | D41487P | | 27 | | D41347P | | 38 | | ALL |
| 0076 | 24 | GK | | | 16-0 | 34-12-21 | D41487P | | 28 | | D41347P | | 39 | | ALL |
| 0077 | 24 | GK | | | 27-0 | 31-31-61 | D41361P | | 14 | | D41371P | | 16 | | 001-099 |
| 0077 | 24 | GK | | | 27-0 | 31-31-32 | D41361P | | 14 | | D41371P | | 16 | | 115-199 |
| 0078 | 24 | GK | | | 9-0 | 31-31-61 | D41361P | | 15 | | D41355P | | 49 | | 001-099 |
| 0078 | 24 | GK | | | 27-0 | SPARE | D41361P | | 15 | | D41371P | | 17 | | 115-199 |
| 0079 | 24 | GK | | | 7-0 | 27-58-31 | D41379P | | 39 | | D41377P | | 5 | | ALL |
| 0080 | 24 | GK | | | 7-0 | 27-58-31 | D41379P | | 40 | | D41381P | | 5 | | ALL |
| 0081 | 22 | GA | | | 26-0 | SPARE | D41491P | | 21 | | D41381P | | 9 | | 115-199 |
| 0082 | 22 | GA | | | 8-0 | 27-81-21 | D41381P | | 10 | | D41377P | | 6 | | ALL |
| 0083 | 22 | GA | | | 18-0 | 22-14-31 | D41909P | | 23 | | D41347P | | 55 | | 115-199 |
| 0085 | 24 | GK | | | 20-0 | 34-33-21 | D41347P | | 32 | | D41379P | | 44 | | ALL |
| 0086 | 24 | GK | | | 24-0 | 34-61-23 | D41347P | | 36 | | D41355P | | 30 | | ALL |
| 0087 | 22 | GA | | | 27-0 | 32-61-21 | D41363P | | 8 | | D41867P | | 3 | | 001-099 |
| 0087 | 24 | GK | | | 27-0 | 32-61-21 | D41363P | | 8 | | D41867P | | 3 | | 115-199 |
| 0088 | 22 | GA | | | 27-0 | 32-61-21 | D41363P | | 9 | | D41867P | | 4 | | 001-099 |
| 0088 | 24 | GK | | | 27-0 | 32-61-21 | D41363P | | 9 | | D41867P | | 4 | | 115-199 |
| 0089 | 22 | GA | | | 27-0 | 32-61-21 | D41363P | | 10 | | D41867P | | 5 | | 001-099 |
| 0089 | 24 | GK | | | 27-0 | 32-61-21 | D41363P | | 10 | | D41867P | | 5 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 23

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|--------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | | |
| 0090 | 22 | | GA | | 16-0 | 32-42-11 | D41347P | 52 | | | | D41487P | 32 | | | ALL | |
| 0091 | 24 | | GK | | 25-0 | 27-32-21 | D41377P | 7 | | | | D41491P | 22 | | | ALL | |
| 0092 | 24 | | GK | | 29-0 | 31-51-21 | D41363P | 1 | | | | D41491P | 26 | | | ALL | |
| 0093 | 24 | | GK | | 29-0 | 31-51-21 | D41363P | 2 | | | | D41491P | 27 | | | ALL | |
| 0094 | 24 | | GK | | 29-0 | 31-51-33 | D41363P | 3 | | | | D41491P | 28 | | | ALL | |
| 0095 | 24 | | GK | | 29-0 | 31-51-41 | D41363P | 4 | | | | D41491P | 29 | | | ALL | |
| 0097 | 22 | | GA | | 29-0 | SPARE | D41355P | 25 | | | | D41909P | 28 | | | 115-199 | |
| 0098 | 24 | | GK | | 18-0 | SPARE | D41881P | 24 | | | | D41487P | 34 | | | 115-199 | |
| 0099 | 24 | | GK | | 20-0 | SPARE | D41347P | 51 | | | | D41379P | 19 | | | 115-199 | |
| 0100 | 22 | | GA | | 16-0 | 32-31-11 | D41347P | 50 | | | | D41487P | 35 | | | ALL | |
| 0101 | 24 | | GK | | 27-0 | 34-53-21 | D41369P | 30 | | | | D41355P | 22 | | | 115-199 | |
| 0102 | 24 | | GK | | 28-0 | 31-31-62 | D41361P | 4 | | | | D41491P | 5 | | | 001-099 | |
| 0102 | 24 | | GK | | 25-0 | SPARE | D41349P | 13 | | | | D41361P | 4 | | | 115-199 | |
| 0103 | 22 | | GA | | 7-0 | SPARE | D41349P | 14 | | | | D41347P | 22 | | | 001, 003-099 | |
| 0103 | 24 | | GK | | 7-0 | SPARE | D41349P | REF | VP | | | D41347P | 22 | | | 002 | |
| 0103 | 24 | | GK | | 7-0 | SPARE | D41349P | 14 | | | | D41347P | 22 | | | 115-199 | |
| 0104 | 22 | | GA | | 20-0 | SPARE | D41351P | 6 | | | | D41367P | 26 | | | 001-099 | |
| 0104 | 24 | | GK | | 20-0 | SPARE | D41351P | 6 | | | | D41367P | 26 | | | 115-199 | |
| 0105 | 22 | | GA | | 22-0 | SPARE | D41351P | 7 | | | | D41369P | 23 | | | 001-099 | |
| 0105 | 24 | | GK | | 10-0 | SPARE | D41351P | 7 | | | | D41881P | 31 | | | 115-199 | |
| 0106 | 22 | | GA | | 21-0 | SPARE | D41867P | 11 | | | | D41349P | 15 | | | 001, 003-099 | |
| 0106 | 22 | | GA | | 21-0 | SPARE | D41867P | 11 | | | | D41349P | REF | VP | | 002 | |
| 0106 | 24 | | GK | | 7-0 | SPARE | D41351P | 37 | | | | D41349P | 15 | | | 115-199 | |
| 0107 | 22 | | GA | | 29-0 | SPARE | D41355P | 26 | | | | D41909P | 29 | | | 115-199 | |
| 0108 | 24 | | GK | | 22-0 | SPARE | D41867P | 33 | | | | D41907P | 26 | | | ALL | |
| 0109 | 24 | | GK | | 25-0 | SPARE | D41361P | 6 | | | | D41349P | 16 | | | 115-199 | |
| 0110 | 24 | | GK | | 29-0 | SPARE | D41363P | 5 | | | | D41491P | 14 | | | 115-199 | |
| 0111 | 22 | | GA | | 17-0 | SPARE | D41487P | 9 | | | | D41339P | 24 | | | 001-099 | |
| 0112 | 24 | | GK | | 23-0 | SPARE | D41367P | 27 | | | | D41491P | 17 | | | 115-199 | |
| 0113 | 24 | | GK | | 22-0 | SPARE | D41367P | 28 | | | | D41487P | 36 | | | 115-199 | |
| 0116 | 24 | | GK | | 18-0 | SPARE | D41369P | 54 | | | | D41379P | 48 | | | 115-199 | |
| 0117 | 24 | | GK | | 26-0 | SPARE | D41909P | 11 | | | | D41371P | 10 | | | 001-099 | |
| 0117 | 24 | | GK | | 13-0 | SPARE | D41369P | 55 | | | | D41371P | 10 | | | 115-199 | |
| 0118 | 24 | | GK | | 23-0 | SPARE | D41867P | 10 | | | | D41487P | 37 | | | 115-199 | |
| 0119 | 24 | | GK | | 27-0 | 32-61-12 | D41867P | 11 | | | | D41363P | 7 | | | 115-199 | |
| 0120 | 24 | | GK | | 27-0 | SPARE | D41371P | 11 | | | | D41355P | 35 | | | 115-199 | |
| 0121 | 20 | | GA | | 18-0 | SPARE | D41909P | 17 | | | | D41347P | 27 | | | 001-099 | |
| 0121 | 24 | | GK | | 21-0 | 34-12-12 | D41371P | 12 | | | | D41347P | CAP | Y | | 115-199 | |
| 0123 | 24 | | GK | | 20-0 | SPARE | D41377P | 14 | | | | D41347P | 31 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 24

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 0125 | 24 | | GK | | 25-0 | SPARE | D41379P | | 50 | | D41491P | | 30 | | 115-199 |
| 0126 | 24 | | GK | | 26-0 | SPARE | D41377P | | 23 | | D41489P | | 19 | | 001-099 |
| 0126 | 24 | | GK | | 26-0 | SPARE | D41379P | | 51 | | D41489P | | 19 | | 115-199 |
| 0127 | 22 | | GA | | 22-0 | 27-09-12 | D41487P | | 12 | | D41367P | | 8 | | 001-099 |
| 0128 | 24 | | GK | | 7-0 | SPARE | D41379P | | 53 | | D41381P | | 1 | | ALL |
| 0129 | 24 | | GK | | 7-0 | SPARE | D41381P | | 11 | | D41379P | | 55 | | 115-199 |
| 0130 | 24 | | GK | | 18-0 | SPARE | D41487P | | 38 | | D41881P | | 22 | | ALL |
| 0131 | 22 | | GA | | 9-0 | 22-14-11 | D41339P | | 20 | | D41349P | | 40 | | ALL |
| 0132 | 24 | | GK | | 16-0 | SPARE | D41487P | | 44 | | D41347P | | 30 | | 115-199 |
| 0134 | 22 | | GA | | 19-0 | SPARE | D41489P | | 21 | | D41347P | | 48 | | 001-099 |
| 0134 | 24 | | GK | | 19-0 | SPARE | D41489P | | 21 | | D41347P | | 48 | | 115-199 |
| 0135 | 24 | | GK | | 23-0 | SPARE | D41491P | | 31 | | D41367P | | 30 | | 115-199 |
| 0136 | 24 | | GK | | 25-0 | SPARE | D41491P | | 32 | | D41377P | | 15 | | ALL |
| 0137 | 24 | | GK | | 29-0 | SPARE | D41491P | | 38 | | D41363P | | 18 | | 001-099 |
| 0137 | 24 | | GK | | 29-0 | SPARE | D41491P | | 38 | | D41363P | | 19 | | 115-199 |
| 0138 | 22 | | GA | | 8-0 | SPARE | D41377P | | 21 | | D41883P | | 1 | | 001-099 |
| 0138 | 22 | | GA | | 23-0 | SPARE | D41351P | | 44 | | D41883P | | 1 | | 115-199 |
| 0139 | 22 | | GA | | 8-0 | SPARE | D41377P | | 22 | | D41883P | | 2 | | 001-099 |
| 0139 | 22 | | GA | | 23-0 | SPARE | D41351P | | 45 | | D41883P | | 2 | | 115-199 |
| 0140 | 22 | | GA | | 23-0 | SPARE | D41351P | | 46 | | D41883P | | 3 | | 115-199 |
| 0141 | 22 | | GA | | 23-0 | SPARE | D41351P | | 47 | | D41883P | | 4 | | 115-199 |
| 0142 | 22 | | GA | | 23-0 | SPARE | D41351P | | 48 | | D41883P | | 5 | | 115-199 |
| 0143 | 22 | | GA | | 23-0 | SPARE | D41351P | | 49 | | D41883P | | 6 | | 115-199 |
| 0144 | 22 | | GA | | 23-0 | SPARE | D41351P | | 50 | | D41883P | | 11 | | 115-199 |
| 0145 | 22 | | GA | | 23-0 | SPARE | D41351P | | 51 | | D41883P | | 31 | | 115-199 |
| 0146 | 24 | | GK | | 29-0 | 31-51-33 | D41363P | | 20 | | D41491P | | 39 | | ALL |
| 0148 | 24 | | GK | | 23-0 | 31-51-41 | D41367P | | 32 | | D41491P | | 40 | | ALL |
| 0149 | 24 | | GK | | 27-0 | 34-53-21 | D41355P | | 1 | | D41487P | | 39 | | ALL |
| 0150 | 22 | | GA | | 16-0 | 22-24-21 | D41379P | | 20 | | D41367P | | 22 | | ALL |
| 0151 | 24 | | GK | | 25-0 | 31-31-62 | D41361P | | 31 | | D41367P | | 25 | | 001-099 |
| 0151 | 24 | | GK | | 25-0 | 31-31-32 | D41367P | | 25 | | D41361P | | 31 | | 115-199 |
| 0152 | 20 | | GA | | 18-0 | 30-33-11 | D41909P | | 31 | | D41347P | | 29 | | ALL |
| 0153 | 20 | | GA | | 18-0 | 30-33-11 | D41909P | | 30 | | D41347P | | 28 | | ALL |
| 0155 | 24 | | GK | | 25-0 | 31-31-62 | D41361P | | 32 | | D41367P | | 33 | | 001-099 |
| 0155 | 24 | | GK | | 25-0 | 31-31-32 | D41361P | | 32 | | D41367P | | 33 | | 115-199 |
| 0156 | 24 | | GK | | 25-0 | 31-31-62 | D41361P | | 33 | | D41367P | | 34 | | 001-099 |
| 0156 | 24 | | GK | | 25-0 | 31-31-32 | D41361P | | 33 | | D41367P | | 34 | | 115-199 |
| 0157 | 24 | | GK | | 25-0 | 31-31-62 | D41361P | | 34 | | D41367P | | 35 | | 001-099 |
| 0157 | 24 | | GK | | 25-0 | 31-31-32 | D41361P | | 34 | | D41367P | | 35 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 25

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 0158 | 24 | | GK | | 25-0 | 31-31-62 | | D41361P | | | | D41367P | | | | 001-099 |
| 0158 | 24 | | GK | | 25-0 | 31-31-32 | | D41361P | | | | D41367P | | | | 115-199 |
| 0159 | 24 | | GK | | 30-0 | 31-31-62 | | D41361P | | | | D41487P | | | | 001-099 |
| 0159 | 22 | | GA | | 27-0 | 31-31-32 | | D41487P | | | | D41361P | | | | 115-199 |
| 0160 | 22 | | GA | | 27-0 | 31-31-32 | | D41487P | | | | D41361P | | | | 115-199 |
| 0161 | 22 | | GA | | 27-0 | 31-31-32 | | D41487P | | | | D41361P | | | | 115-199 |
| 0162 | 24 | | GK | | 25-0 | 31-31-62 | | D41361P | | | | D41367P | | | | 001-099 |
| 0162 | 24 | | GK | | 25-0 | 31-31-32 | | D41361P | | | | D41367P | | | | 115-199 |
| 0163 | 24 | | GK | | 25-0 | 31-31-62 | | D41361P | | | | D41367P | | | | 001-099 |
| 0163 | 24 | | GK | | 25-0 | 31-31-32 | | D41361P | | | | D41367P | | | | 115-199 |
| 0164 | 24 | | GK | | 25-0 | 31-31-62 | | D41361P | | | | D41367P | | | | 001-099 |
| 0164 | 24 | | GK | | 25-0 | 31-31-32 | | D41361P | | | | D41367P | | | | 115-199 |
| 0165 | 24 | | GK | | 25-0 | 31-31-62 | | D41361P | | | | D41367P | | | | 001-099 |
| 0165 | 24 | | GK | | 25-0 | 31-31-32 | | D41361P | | | | D41367P | | | | 115-199 |
| 0166 | 22 | | GA | | 27-0 | 31-31-32 | | D41361P | | | | D41487P | | | | 115-199 |
| 0167 | 24 | | GK | | 8-0 | 27-51-31 | | D41377P | | | | D41883P | | | | 001-099 |
| 0167 | 20 | | GA | | 8-0 | 27-51-31 | | D41377P | | | | D41883P | | | | 115-199 |
| 0168 | 22 | | GA | | 8-0 | 27-51-21 | | D41377P | | | | D41883P | | | | 001-099 |
| 0168 | 20 | | GA | | 8-0 | 27-51-21 | | D41377P | | | | D41883P | | | | 115-199 |
| 0169 | 22 | | GA | | 8-0 | 27-51-21 | | D41377P | | | | D41883P | | | | 001-099 |
| 0169 | 20 | | GA | | 8-0 | 27-51-21 | | D41377P | | | | D41883P | | | | 115-199 |
| 0170 | 24 | | GK | | 8-0 | SPARE | | D41377P | | | | D41883P | | | | 115-199 |
| 0171 | 24 | | GK | | 8-0 | SPARE | | D41381P | | | | D41883P | | | | ALL |
| 0173 | 24 | | GK | | 18-0 | SPARE | | D41881P | | | | D41491P | | | | 115-199 |
| 0174 | 24 | | GK | | 23-0 | 21-44-11 | | D41867P | | | | D41487P | | | | ALL |
| 0175 | 22 | | GA | | 10-0 | 22-15-12 | | D41339P | | | | D41881P | | | | 001-099 |
| 0175 | 22 | | GA | | 10-0 | 22-15-12 | | D41339P | | | | D41881P | | | | 115-199 |
| 0176 | 22 | | GA | | 9-0 | 22-15-12 | | D41349P | | | | D41881P | | | | 001-099 |
| 0176 | 22 | | GA | | 9-0 | 22-15-12 | | D41349P | | | | D41881P | | | | 115-199 |
| 0177 | 22 | | GA | | 22-0 | SPARE | | D41377P | | | | D41339P | | | | 115-199 |
| 0178 | 22 | | GA | | 22-0 | 22-41-11 | | D41867P | | | | D41339P | | | | ALL |
| 0179 | 22 | | GA | | 21-0 | 22-41-11 | | D41349P | | | | D41867P | | | | ALL |
| 0180 | 22 | | GA | | 17-0 | 27-41-21 | | D41367P | | | | D41883P | | | | ALL |
| 0181 | 22 | | GA | | 19-0 | 29-32-11 | | D41867P | | | | SP00011 | | | | ALL |
| 0182 | 22 | | GA | | 10-0 | 27-09-13 | | D41867P | | | | D41367P | | | | ALL |
| 0184 | 22 | | GA | | 8-0 | 27-81-31 | | D41377P | | | | D41381P | | | | ALL |
| 0185 | 24 | | GK | | 26-0 | 24-22-22 | | D41883P | | | | D41909P | | | | ALL |
| 0186 | 22 | | GA | | 27-0 | 32-61-12 | | D41355P | | | | D41487P | | | | ALL |
| 0187 | 22 | | GA | | 27-0 | 32-61-12 | | D41355P | | | | D41487P | | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 26

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|-----------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | | |
| 0188 | 24 | | GK | | 10-0 | 32-61-12 | D41355P | | 38 | | | D41363P | 7 | | | 001-099 | |
| 0188 | 24 | | GK | | 27-0 | 32-61-12 | D41355P | | 38 | | | D41867P | 23 | | | 115-199 | |
| 0189 | 22 | | GA | | 27-0 | SPARE | D41363P | | 28 | | | D41867P | 24 | | | ALL | |
| 0190 | 22 | | GA | | 27-0 | 32-61-12 | D41363P | | 25 | | | D41867P | 25 | | | ALL | |
| 0191 | 24 | | GK | | 27-0 | 32-61-12 | D41363P | | 26 | | | D41867P | 26 | | | ALL | |
| 0192 | 24 | | GK | | 27-0 | 32-61-12 | D41363P | | 27 | | | D41867P | 27 | | | ALL | |
| 0193 | 22 | | GA | | 29-0 | 22-14-31 | D41355P | | 37 | | | D41909P | 19 | | | ALL | |
| 0194 | 22 | | GA | | 26-0 | 24-51-24 | D41381P | | 20 | | | D41909P | 20 | | | ALL | |
| 0195 | 22 | | GA | | 9-0 | SPARE | D41881P | | 23 | | | D41349P | 33 | | | 115-199 | |
| 0197 | 22 | | GA | | 27-0 | 27-23-21 | D41489P | | 4 | | | D41381P | 2 | | | ALL | |
| 0198 | 22 | | GA | | 27-0 | 27-23-21 | D41489P | | 5 | | | D41381P | 3 | | | ALL | |
| 0199 | 24 | | GK | | 17-0 | SPARE | D41487P | | 41 | | | D41349P | 41 | | | 001, 003-099 | |
| 0199 | 24 | | GK | | 17-0 | SPARE | D41487P | | 41 | | | D41349P | REF | VP | | 002 | |
| 0200 | 22 | | GA | | 9-0 | 22-11-22 | D41907P | | 14 | | | D41349P | 38 | | | ALL | |
| 0201 | 22 | | GA | | 9-0 | 22-11-22 | D41907P | | 15 | | | D41349P | 39 | | | ALL | |
| 0202 | 22 | | GA | | 10-0 | 22-11-22 | D41907P | | 16 | | | D41339P | 2 | | | ALL | |
| 0203 | 22 | | GA | | 9-0 | 22-14-31 | D41907P | | 17 | | | D41349P | 42 | | | ALL | |
| 0204 | 22 | | GA | | 10-0 | 22-14-11 | D41339P | | 26 | | | D41907P | 18 | | | 001-099 | |
| 0204 | 22 | | GA | | 10-0 | 22-14-11 | D41907P | | 18 | | | D41339P | 26 | | | 115-199 | |
| 0205 | 22 | | GA | | 7-0 | 22-14-11 | D41347P | | 53 | | | D41349P | 44 | | | ALL | |
| 0206 | 22 | | GA | | 8-0 | 22-14-11 | D41347P | | 54 | | | D41339P | 19 | | | 001-099 | |
| 0206 | 22 | | GA | | 8-0 | 22-14-11 | D41339P | | 19 | | | D41347P | 54 | | | 115-199 | |
| 0207 | 22 | | GA | | 18-0 | 22-14-31 | D41909P | | 23 | | | D41347P | 55 | | | 001-099 | |
| 0208 | 24 | | GK | | 25-0 | 31-41-24 | D41867P | | 29 | | | D41491P | 45 | | | ALL | |
| 0209 | 22 | | GA | | 32-0 | 35-11-13 | D41909P | | 25 | | | D02284 | 1 | | | 115-199 | |
| 0210 | 24 | | GK | | 23-0 | 31-51-21 | D41489P | | 3 | | | D41491P | 33 | | | ALL | |
| 0211 | 24 | | GK | | 23-0 | 34-12-12 | D41489P | | 6 | | | D41491P | CAP | Y | | 115-199 | |
| 0213 | 24 | | GK | | 8-0 | 24-22-22 | D41377P | | 48 | | | D41883P | 37 | | | 001-099 | |
| 0213 | 24 | | GK | | 8-0 | 24-22-22 | D41381P | | 19 | | | D41883P | 37 | | | 115-199 | |
| 0214 | 24 | | GK | | 8-0 | 24-22-22 | D41883P | | 39 | | | D41377P | 10 | | | ALL | |
| 0215 | 24 | | GK | | 26-0 | SPARE | D41909P | | 32 | | | D41883P | 40 | | | ALL | |
| 0216 | 22 | | GA | | 9-0 | SPARE | D41339P | | 18 | | | D41349P | 37 | | | 001, 003-099, 115-199 | |
| 0216 | 22 | | GA | | 9-0 | SPARE | D41339P | | 18 | | | D41349P | REF | VP | | 002 | |
| 0217 | 24 | | GK | | 10-0 | 32-61-12 | D41355P | | 23 | | | D41363P | 6 | | | 001-099 | |
| 0217 | 22 | | GA | | 10-0 | 32-61-12 | D41355P | | 23 | | | D41363P | 6 | | | 115-199 | |
| 0220 | 22 | | GA | | 20-0 | 34-61-25 | D41907P | | 13 | | | D41909P | 42 | | | ALL | |
| 0221 | 24 | | GK | | 27-0 | 32-61-12 | D41867P | | 34 | | | D41363P | 16 | | | 001-099 | |
| 0221 | 22 | | GA | | 27-0 | 32-61-11 | D41867P | | 34 | | | D41363P | 32 | | | 115-199 | |
| 0222 | 24 | | GK | | 27-0 | 32-61-12 | D41867P | | 35 | | | D41363P | 31 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 27

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 0222 | 22 | | GA | | 27-0 | 32-61-11 | | D41867P | | | | D41363P | 31 | | | 115-199 |
| 0223 | 22 | | GA | | 27-0 | 32-61-12 | | D41867P | | | | D41363P | 29 | | | 001-099 |
| 0223 | 22 | | GA | | 27-0 | 32-61-12 | | D41867P | | | | D41363P | 30 | | | 115-199 |
| 0224 | 22 | | GA | | 27-0 | 32-61-12 | | D41867P | | | | D41363P | 30 | | | 001-099 |
| 0224 | 22 | | GA | | 27-0 | 32-61-12 | | D41867P | | | | D41363P | 29 | | | 115-199 |
| 0225 | 22 | | GA | | 20-0 | 34-61-21 | | D41907P | | | | D41909P | 22 | | | 001-099 |
| 0226 | 22 | | GA | | 20-0 | 34-61-21 | | D41907P | | | | D41909P | 24 | | | 001-099 |
| 0227 | 24 | | GK | | 9-0 | 73-21-22 | | D41349P | | | | D41907P | 4 | | | 001-099 |
| 0227 | 24 | | GK | | 9-0 | 73-21-22 | | D41349P | | | | D41339P | 34 | | | 115-199 |
| 0228 | 24 | | GK | | 9-0 | 73-21-22 | | D41907P | | | | D41349P | 45 | | | 001-099 |
| 0228 | 24 | | GK | | 9-0 | 73-21-22 | | D41349P | | | | D41339P | 35 | | | 115-199 |
| 0241 | 24 | | GK | | 7-0 | 27-58-31 | | D41381P | | | | D41379P | 16 | | | ALL |
| 0242 | 20 | | GA | | 3-0 | 28-41-11 | | D05660 | | | | GD02095 | DC.. | E | | ALL |
| 0244 | 22 | | GA | | 15-0 | 30-34-22 | | D41489P | | | | D41909P | 43 | | | ALL |
| 0245 | 22 | | GA | | 15-0 | 30-34-22 | | D41489P | | | | D41909P | 44 | | | ALL |
| 0246 | 22 | | GA | | 15-0 | 30-34-22 | | D41489P | | | | D41909P | 45 | | | ALL |
| 0247 | 22 | | GA | | 16-0 | 34-12-12 | | S10471 | | C | | D41339P | 24 | | | 115-199 |
| 0248 | 20 | | GA | | 3-0 | 34-12-12 | | S10471 | | C | | GD02243 | DC.. | E | | 115-199 |
| 0249 | 22 | | GA | | 16-0 | 34-12-22 | | S10471 | | C | | D41347P | 27 | | | 115-199 |
| 0250 | 20 | | GA | | 3-0 | 34-12-22 | | S10471 | | C | | GD02243 | DC.. | E | | 115-199 |
| 0251 | 22 | | GA | | 20-0 | 34-16-11 | | S10471 | | C | | D41491P | 12 | | | 115-199 |
| 0252 | 22 | | GA | | 20-0 | 34-16-11 | | S10471 | | C | | D41491P | 13 | | | 115-199 |
| 0253 | 22 | | GA | | 10-0 | 27-09-14 | | D41867P | | | | D41367P | 43 | | | ALL |
| 0254 | 22 | | GA | | 10-0 | 27-09-14 | | D41867P | | | | D41367P | 44 | | | ALL |
| 0255 | 22 | | GA | | 10-0 | 27-09-14 | | D41867P | | | | D41367P | 48 | | | ALL |
| 0256 | 22 | | GA | | 10-0 | 27-09-14 | | D41867P | | | | D41367P | 49 | | | ALL |
| 0257 | 22 | | GA | | 10-0 | 27-09-14 | | D41867P | | | | D41367P | 50 | | | ALL |
| 0258 | 22 | | GA | | 10-0 | 27-09-14 | | D41867P | | | | D41367P | 51 | | | ALL |
| 0261 | 22 | | GA | | 27-0 | SPARE | | D41381P | | | | D41489P | 10 | | | 001-099 |
| 0262 | 22 | | GA | | 8-0 | SPARE | | D41381P | | | | D41377P | 20 | | | 001-099 |
| 0264 | 24 | | GK | | 23-0 | SPARE | | D41489P | | | | D41491P | 50 | | | 001-099 |
| 0265 | 22 | | GA | | 25-3 | 31-31-61 | | D41881P | | | | D41361P | 24 | | | 010-099 |
| 0268 | 22 | | GA | | 8-0 | 27-81-31 | | D41377P | | | | D01251 | 4 | | | ALL |
| 0269 | 22 | | GA | | 8-0 | 27-51-21 | | D41377P | | | | D01251 | 5 | | | ALL |
| 0273 | 20 | | GA | | 26-0 | 23-32-01 | | D41909P | | | | SP26007 | | 9 | | ALL |
| 0274 | 20 | | GA | | 26-0 | 23-32-01 | | D41909P | | | | SP26003 | | 9 | | ALL |
| 0275 | 20 | | GA | | 26-0 | 23-32-01 | | D41909P | | | | SP26005 | | 9 | | ALL |
| 0281 | 24 | | GK | | 27-0 | 23-51-14 | | D41371P | | | | D41355P | 24 | | | 001-099 |
| 0282 | 20 | | GA | | 27-0 | 23-51-14 | | D41371P | | | | D41355P | 34 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 28

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | | | To | | | | | Effectivity | |
|------------|-------------|----|-------|--------------------------------------|------|----------|---------|-------|------|------|--------|---------|------|------|-------------|------------------|
| | Wire No. | GA | CO TY | | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | | Splice |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | | |
| 0283 | 22 | GA | | | 23-0 | 34-51-21 | D43007P | | 1 | | | D43005P | 1 | | | 001-099 |
| 0284 | 24 | GK | | | 23-0 | 34-51-21 | D43007P | | 8 | | | D43005P | 8 | | | 001-099 |
| 0285 | 22 | GA | | | 23-0 | SPARE | D43007P | | 15 | | | D43005P | 15 | | | 001-099 |
| 0295 | 22 | PA | | | 5-9 | 34-61-25 | D41909P | | 27 | | | D41339P | 17 | | | 115-199 |
| 0296 | 24 | PK | | | 18-0 | 34-61-26 | D43017P | | 2 | | | D43021P | 2 | | | 115-199 |
| 0297 | 24 | PK | | | 18-0 | 34-61-26 | D43017P | | 18 | | | D43021P | 18 | | | 115-199 |
| 0298 | 24 | PK | | | 18-0 | 34-61-26 | D43017P | | 19 | | | D43021P | 19 | | | 115-199 |
| 0299 | 24 | PK | | | 18-0 | 34-61-26 | D43017P | | 29 | | | D43021P | 29 | | | 115-199 |
| 0300 | 24 | PK | | | 18-0 | 34-61-26 | D43017P | | 30 | | | D43021P | 30 | | | 115-199 |
| 0306 | 24 | PK | | | 18-0 | 34-61-26 | D43017P | | 1 | | | D43021P | 1 | | | 115-199 |
| 0329 | 24 | GK | | | 10-0 | 34-45-01 | D41339P | | 25 | | | D41881P | 20 | | | 001-002, 115-199 |
| 0329 | 24 | GK | | | 10-0 | SPARE | D41339P | | 25 | | | D41881P | 20 | | | 003-099 |
| 0330 | 24 | GK | | | 10-0 | 34-45-01 | D41339P | | 27 | | | D41881P | 21 | | | 001-002, 115-199 |
| 0330 | 24 | GK | | | 10-0 | SPARE | D41339P | | 27 | | | D41881P | 21 | | | 003-099 |
| 0331 | 24 | GK | | | 8-0 | 34-45-01 | D41339P | | 54 | | | D41347P | 26 | | | ALL |
| 0332 | 22 | GA | | | 23-0 | SPARE | D43005P | | 7 | | | D41339P | 12 | | | 115-199 |
| 0333 | 24 | GK | | | 23-0 | SPARE | D43005P | | 8 | | | D41339P | 13 | | | 115-199 |
| 0341 | 24 | GK | | | 25-0 | SPARE | D41345P | | 44 | | | D41355P | 46 | | | 001, 003-099 |
| 0341 | 24 | GK | | | 25-0 | SPARE | D41345P | REF | VP | | | D41355P | 46 | | | 002 |
| 0346 | 22 | CQ | | | 20-0 | 34-22-26 | D41347P | | 31 | | | D41909P | 55 | | | 002 |
| 0347 | 22 | GA | | | 25-3 | 34-25-12 | D41361P | | 11 | | | D41345P | 44 | | | 002 |
| 0348 | 22 | CQ | | | 20-0 | 34-25-12 | D41487P | | 50 | | | D41361P | 12 | | | 002 |
| 0392 | 22 | GA | | | 24-8 | 31-31-61 | D41379P | | 9 | | | D43315P | 4 | | | 010-099 |
| 0393 | 22 | GA | | | 24-8 | 31-31-61 | D41379P | | 31 | | | D43315P | 5 | | | 010-099 |
| 0453 | 22 | CQ | | | 20-0 | 34-22-28 | D41909P | | 10 | | | D41349P | 13 | | | 002 |
| 0486 | 22 | GA | | | 26-2 | 31-31-61 | D41909P | | 4 | | | D43315P | 6 | | | 010-099 |
| 0535 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 1 | | | D03927 | 5 | | | ALL |
| 0536 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 2 | | | D03927 | 6 | | | ALL |
| 0537 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 3 | | | D03927 | 15 | | | ALL |
| 0538 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 13 | | | D03927 | 13 | | | ALL |
| 0539 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 14 | | | D03927 | 14 | | | ALL |
| 0540 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 15 | | | D03927 | 17 | | | ALL |
| 0541 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 16 | | | D03927 | 18 | | | ALL |
| 0542 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 17 | | | D03927 | 16 | | | ALL |
| 0543 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 18 | | | D03927 | 2 | | | ALL |
| 0544 | 22 | GA | | | 9-0 | 34-12-62 | D42233P | | 19 | | | D03927 | 1 | | | ALL |
| 2001B | 24 | GL | AA | | 26-0 | SPARE | D41489P | | 2 | | | D41379P | 28 | | | 115-199 |
| 2001R | 24 | GL | AA | | 0-0 | SPARE | D41489P | | 1 | | | D41379P | 27 | | | 115-199 |
| 2002B | 24 | GL | AB | | 18-0 | SPARE | D41379P | | 29 | | | D41369P | 27 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 29

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity | |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 2002R | 24 | GL | AB | | 0-0 | SPARE | D41379P | 30 | | | D41369P | 28 | | | 115-199 | |
| 2003B | 22 | GB | AC | | 25-0 | 22-24-21 | D41489P | 8 | | | D41367P | 24 | | | ALL | |
| 2003R | 22 | GB | AC | | 0-0 | 22-24-21 | D41489P | 7 | | | D41367P | 23 | | | ALL | |
| 2004B | 22 | GB | AD | | 24-0 | 35-11-13 | D41369P | 38 | | | D02284 | 2 | | | ALL | |
| 2004R | 22 | GB | AD | | 0-0 | 35-11-13 | D41369P | 39 | | | D02284 | 3 | | | ALL | |
| 2005B | 22 | GB | IN | | 25-0 | 35-11-13 | D04012 | 2 | | | D41369P | 20 | | | 115-199 | |
| 2005R | 22 | GB | IN | | 0-0 | 35-11-13 | D04012 | 1 | | | D41369P | 19 | | | 115-199 | |
| 2006B | 22 | GB | AM | | 20-0 | 22-12-21 | D41907P | 28 | | | D41367P | 42 | | | ALL | |
| 2006R | 22 | GB | AM | | 0-0 | 22-12-21 | D41907P | 27 | | | D41367P | 41 | | | ALL | |
| 2007B | 24 | GL | AH | | 25-0 | 27-32-21 | D41377P | 40 | | | D41491P | 9 | | | 001-099 | |
| 2007B | 24 | GL | AH | | 25-0 | 27-32-21 | D41379P | 7 | | | D41491P | 9 | | | 115-199 | |
| 2007R | 24 | GL | AH | | 0-0 | 27-32-21 | D41377P | 39 | | | D41491P | 8 | | | 001-099 | |
| 2007R | 24 | GL | AH | | 0-0 | 27-32-21 | D41379P | 13 | | | D41491P | 8 | | | 115-199 | |
| 2008B | 24 | GL | CP | | 27-0 | SPARE | D41487P | 55 | | | D41361P | 47 | | | 115-199 | |
| 2008R | 24 | GL | CP | | 0-0 | SPARE | D41487P | 46 | | | D41361P | 48 | | | 115-199 | |
| 2009B | 24 | GL | CQ | | 27-0 | 23-21-11 | D41355P | 26 | | | D41371P | 12 | | | 001-099 | |
| 2009R | 24 | GL | CQ | | 0-0 | 23-21-11 | D41355P | 25 | | | D41371P | 11 | | | 001-099 | |
| 2501B | 24 | G2 | BA | | 20-0 | 22-21-21 | D41351P | 2 | | | D41367P | 11 | | | ALL | |
| 2501R | 24 | G2 | BA | | 0-0 | 22-21-21 | D41351P | 1 | | | D41367P | 10 | | | ALL | |
| 2501Z | | | BA | | 0-0 | 22-21-21 | D41351P | 3 | | | D41367P | 12 | | | ALL | |
| 2502B | 24 | G2 | BB | | 21-0 | 23-51-13 | D41371P | 14 | | | D41347P | 10 | | | ALL | |
| 2502R | 24 | G2 | BB | | 0-0 | 23-51-13 | D41371P | 13 | | | D41347P | 9 | | | ALL | |
| 2502Z | | | BB | | 0-0 | 23-51-13 | D41371P | 15 | | | D41347P | 11 | | | ALL | |
| 2503B | 24 | G2 | BC | | 7-0 | 27-58-31 | D41379P | 41 | | | D41381P | 6 | | | ALL | |
| 2503R | 24 | G2 | BC | | 0-0 | 27-58-31 | D41379P | 42 | | | D41381P | 7 | | | ALL | |
| 2503Z | | | BC | | 0-0 | 27-58-31 | D41379P | 43 | | | D41381P | 8 | | | ALL | |
| 2504B | 24 | G2 | DD | | 13-0 | 23-41-11 | D41867P | 6 | | | D41371P | 30 | | | 001-099 | |
| 2504R | 24 | G2 | DD | | 0-0 | 23-41-11 | D41867P | 7 | | | D41371P | 31 | | | 001-099 | |
| 2504Z | | | DD | | 0-0 | 23-41-11 | D41867P | 9 | | | D41371P | 33 | | | 001-099 | |
| 2505B | 24 | G2 | DC | | 16-0 | 23-41-12 | SM00005 | | 9 | | D41371P | 23 | | | 001-099 | |
| 2505R | 24 | G2 | DC | | 0-0 | 23-41-12 | SM00004 | | 9 | | D41371P | 22 | | | 001-099 | |
| 2505Z | | | DC | | 0-0 | 23-41-12 | SM00006 | | 9 | | D41371P | 25 | | | 001-099 | |
| 2506B | 24 | G2 | DB | | 23-0 | 23-41-12 | SM00002 | | 9 | | D41371P | 19 | | | 001-099 | |
| 2506R | 24 | G2 | DB | | 0-0 | 23-41-12 | SM00001 | | 9 | | D41371P | 18 | | | 001-099 | |
| 2506Z | | | DB | | 0-0 | 23-41-12 | SM00003 | | 9 | | D41371P | 21 | | | 001-099 | |
| 2507B | 24 | G2 | DE | | 27-0 | 23-41-11 | D41363P | 14 | | | D41371P | 26 | | | 001-099 | |
| 2507R | 24 | G2 | DE | | 0-0 | 23-41-11 | D41363P | 15 | | | D41371P | 27 | | | 001-099 | |
| 2507Z | | | DE | | 0-0 | 23-41-11 | D41363P | 17 | | | D41371P | 28 | | | 001-099 | |
| 2508B | 24 | G2 | BH | | 8-0 | 24-41-11 | D41377P | 50 | | | D41381P | 50 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 30

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | Effectivity |
|------------|-------------|----|-------|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 2508R | 24 | G2 | BH | | 0-0 | 24-41-11 | D41377P | 49 | | | D41381P | 49 | | | 001-099 |
| 2508Z | | | BH | | 0-0 | 24-41-11 | D41377P | 51 | | | D41381P | 51 | | | 001-099 |
| 2509B | 24 | G2 | FY | | 9-0 | 34-12-62 | D42233P | 4 | | | D03927 | 10 | | | 001-099 |
| 2509B | 24 | G2 | AY | | 9-0 | 34-12-62 | D42233P | 4 | | | D03927 | 10 | | | 115-199 |
| 2509R | 24 | G2 | FY | | 0-0 | 34-12-62 | D42233P | 5 | | | D03927 | 7 | | | 001-099 |
| 2509R | 24 | G2 | AY | | 0-0 | 34-12-62 | D42233P | 5 | | | D03927 | 7 | | | 115-199 |
| 2509Z | | | FY | | 0-0 | 34-12-62 | D42233P | 6 | | | D03927 | DED | | | 001-099 |
| 2509Z | | | AY | | 0-0 | 34-12-62 | D42233P | 6 | | | D03927 | DED | | | 115-199 |
| 2510B | 24 | G2 | FZ | | 9-0 | 34-12-62 | D42233P | 8 | | | D03927 | 11 | | | 001-099 |
| 2510B | 24 | G2 | AZ | | 9-0 | 34-12-62 | D42233P | 8 | | | D03927 | 11 | | | 115-199 |
| 2510R | 24 | G2 | FZ | | 0-0 | 34-12-62 | D42233P | 7 | | | D03927 | 8 | | | 001-099 |
| 2510R | 24 | G2 | AZ | | 0-0 | 34-12-62 | D42233P | 7 | | | D03927 | 8 | | | 115-199 |
| 2510Z | | | FZ | | 0-0 | 34-12-62 | D42233P | 9 | | | D03927 | DED | | | 001-099 |
| 2510Z | | | AZ | | 0-0 | 34-12-62 | D42233P | 9 | | | D03927 | DED | | | 115-199 |
| 2511B | 24 | G2 | BD | | 9-0 | 34-12-62 | D42233P | 11 | | | D03927 | 12 | | | ALL |
| 2511R | 24 | G2 | BD | | 0-0 | 34-12-62 | D42233P | 10 | | | D03927 | 9 | | | ALL |
| 2511Z | | | BD | | 0-0 | 34-12-62 | D42233P | 12 | | | D03927 | DED | | | ALL |
| 3501B | 24 | G3 | DA | | 27-0 | 23-51-12 | D41355P | 14 | | | D41371P | 6 | | | ALL |
| 3501R | 24 | G3 | DA | | 0-0 | 23-51-12 | D41355P | 13 | | | D41371P | 5 | | | ALL |
| 3501Y | 24 | G3 | DA | | 0-0 | 23-51-12 | D41355P | 15 | | | D41371P | 7 | | | ALL |
| 3501Z | | | DA | | 0-0 | 23-51-12 | D41355P | 16 | | | D41371P | 8 | | | ALL |
| 3502B | 24 | G3 | DB | | 24-0 | 23-41-12 | D41371P | 19 | | | SM00002 | | 9 | | 115-199 |
| 3502R | 24 | G3 | DB | | 0-0 | 23-41-12 | D41371P | 18 | | | SM00001 | | 9 | | 115-199 |
| 3502Y | 24 | G3 | DB | | 0-0 | 23-41-12 | D41371P | 20 | | | SM00003 | | 9 | | 115-199 |
| 3502Z | | | DB | | 0-0 | 23-41-12 | D41371P | 21 | | | SM00003 | DED | | | 115-199 |
| 3503B | 24 | G3 | DC | | 17-0 | 23-41-12 | D41371P | 23 | | | SM00005 | | 9 | | 115-199 |
| 3503R | 24 | G3 | DC | | 0-0 | 23-41-12 | D41371P | 22 | | | SM00004 | | 9 | | 115-199 |
| 3503Y | 24 | G3 | DC | | 0-0 | 23-41-12 | D41371P | 24 | | | SM00006 | | 9 | | 115-199 |
| 3503Z | | | DC | | 0-0 | 23-41-12 | D41371P | 25 | | | SM00006 | DED | | | 115-199 |
| 3504B | 24 | G3 | DD | | 13-0 | 23-41-11 | D41867P | 6 | | | D41371P | 30 | | | 115-199 |
| 3504R | 24 | G3 | DD | | 0-0 | 23-41-11 | D41867P | 7 | | | D41371P | 31 | | | 115-199 |
| 3504Y | 24 | G3 | DD | | 0-0 | 23-41-11 | D41867P | 8 | | | D41371P | 32 | | | 115-199 |
| 3504Z | | | DD | | 0-0 | 23-41-11 | D41867P | 9 | | | D41371P | 33 | | | 115-199 |
| 3505B | 24 | G3 | DE | | 27-0 | 23-41-11 | D41363P | 14 | | | D41371P | 26 | | | 115-199 |
| 3505R | 24 | G3 | DE | | 0-0 | 23-41-11 | D41363P | 15 | | | D41371P | 27 | | | 115-199 |
| 3505Y | 24 | G3 | DE | | 0-0 | 23-41-11 | D41363P | 16 | | | D41371P | 29 | | | 115-199 |
| 3505Z | | | DE | | 0-0 | 23-41-11 | D41363P | 17 | | | D41371P | 28 | | | 115-199 |
| 4001B | 24 | G4 | EA | | 8-0 | SPARE | D41377P | 21 | | | D41883P | 17 | | | 115-199 |
| 4001G | 24 | G4 | EA | | 0-0 | SPARE | D41377P | 19 | | | D41883P | 15 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 31

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--------------------------------------|-------------|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | | |
| 4001R | 24 | | G4 | EA | 0-0 | SPARE | D41377P | 22 | | | D41883P | 18 | | | 115-199 | |
| 4001Y | 24 | | G4 | EA | 0-0 | SPARE | D41377P | 20 | | | D41883P | 16 | | | 115-199 | |
| 4001Z | | | | EA | 0-0 | SPARE | D41377P | 23 | | | D41883P | 19 | | | 115-199 | |
| 5001B | 24 | | G2 | GA | 22-0 | 31-41-22 | D41369P | 3 | | | D41345P | 3 | | | ALL | |
| 5001R | 24 | | G2 | GA | 0-0 | 31-41-22 | D41369P | 2 | | | D41345P | 2 | | | ALL | |
| 5001Z | | | | GA | 0-0 | 31-41-22 | D41369P | 1 | | | D41345P | 1 | | | ALL | |
| 5002B | 24 | | G2 | GB | 18-0 | 31-41-22 | D41369P | 5 | | | D41379P | 5 | | | ALL | |
| 5002R | 24 | | G2 | GB | 0-0 | 31-41-22 | D41369P | 4 | | | D41379P | 4 | | | ALL | |
| 5002Z | | | | GB | 0-0 | 31-41-22 | D41369P | 6 | | | D41379P | 6 | | | ALL | |
| 5003B | 24 | | G2 | GC | 22-0 | 34-61-24 | D41369P | 8 | | | D41345P | 8 | | | ALL | |
| 5003R | 24 | | G2 | GC | 0-0 | 34-61-24 | D41369P | 7 | | | D41345P | 7 | | | ALL | |
| 5003Z | | | | GC | 0-0 | 34-61-24 | D41369P | 9 | | | D41345P | 9 | | | ALL | |
| 5004B | 24 | | G2 | GD | 26-0 | 34-61-24 | D41363P | 12 | | | D41345P | 12 | | | ALL | |
| 5004R | 24 | | G2 | GD | 0-0 | 34-61-24 | D41363P | 11 | | | D41345P | 11 | | | ALL | |
| 5004Z | | | | GD | 0-0 | 34-61-24 | D41363P | 13 | | | D41345P | 13 | | | ALL | |
| 5005B | 24 | | G2 | GE | 22-0 | 34-61-25 | D41369P | 15 | | | D41345P | 15 | | | ALL | |
| 5005R | 24 | | G2 | GE | 0-0 | 34-61-25 | D41369P | 14 | | | D41345P | 14 | | | ALL | |
| 5005Z | | | | GE | 0-0 | 34-61-25 | D41369P | 16 | | | D41345P | 16 | | | ALL | |
| 5006B | 24 | | G2 | GF | 25-0 | 34-61-13 | D41355P | 5 | | | D41345P | 5 | | | ALL | |
| 5006R | 24 | | G2 | GF | 0-0 | 34-61-13 | D41355P | 4 | | | D41345P | 4 | | | ALL | |
| 5006Z | | | | GF | 0-0 | 34-61-13 | D41355P | 6 | | | D41345P | 6 | | | ALL | |
| 5007B | 24 | | G2 | GG | 25-0 | 34-22-29 | D41355P | 8 | | | D41345P | 19 | | | ALL | |
| 5007R | 24 | | G2 | GG | 0-0 | 34-22-29 | D41355P | 7 | | | D41345P | 18 | | | ALL | |
| 5007Z | | | | GG | 0-0 | 34-22-29 | D41355P | 9 | | | D41345P | 20 | | | ALL | |
| 5008B | 24 | | G2 | GH | 22-0 | 34-22-29 | D41379P | 2 | | | D41345P | 46 | | | ALL | |
| 5008R | 24 | | G2 | GH | 0-0 | 34-22-29 | D41379P | 1 | | | D41345P | 48 | | | ALL | |
| 5008Z | | | | GH | 0-0 | 34-22-29 | D41379P | 3 | | | D41345P | 47 | | | ALL | |
| 5009B | 24 | | G2 | GI | 18-0 | SPARE | D41487P | 3 | | | D41881P | 16 | | | ALL | |
| 5009R | 24 | | G2 | GI | 0-0 | SPARE | D41487P | 4 | | | D41881P | 17 | | | ALL | |
| 5009Z | | | | GI | 0-0 | SPARE | D41487P | 5 | | | D41881P | 18 | | | ALL | |
| 5010B | 24 | | G2 | GJ | 25-0 | 34-53-11 | D41361P | 2 | | | D41345P | 22 | | | ALL | |
| 5010R | 24 | | G2 | GJ | 0-0 | 34-53-11 | D41361P | 1 | | | D41345P | 21 | | | ALL | |
| 5010Z | | | | GJ | 0-0 | 34-53-11 | D41361P | 3 | | | D41345P | 23 | | | ALL | |
| 5011B | 24 | | G2 | GK | 21-0 | SPARE | D41349P | 27 | | | D41369P | 23 | | | 115-199 | |
| 5011R | 24 | | G2 | GK | 0-0 | SPARE | D41349P | 26 | | | D41369P | 24 | | | 115-199 | |
| 5011Z | | | | GK | 0-0 | SPARE | D41349P | 28 | | | D41369P | 25 | | | 115-199 | |
| 5012B | 24 | | G2 | GL | 25-0 | 34-53-21 | D41355P | 11 | | | D41345P | 25 | | | ALL | |
| 5012R | 24 | | G2 | GL | 0-0 | 34-53-21 | D41355P | 10 | | | D41345P | 24 | | | ALL | |
| 5012Z | | | | GL | 0-0 | 34-53-21 | D41355P | 12 | | | D41345P | 26 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 32

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 5013B | 24 | | G2 | GM | 17-0 | 27-32-21 | D41345P | 28 | | | D41491P | 2 | | | ALL |
| 5013R | 24 | | G2 | GM | 0-0 | 27-32-21 | D41345P | 27 | | | D41491P | 1 | | | ALL |
| 5013Z | | | | GM | 0-0 | 27-32-21 | D41345P | 29 | | | D41491P | 3 | | | ALL |
| 5014B | 24 | | G2 | GN | 20-0 | 22-22-21 | D41345P | 32 | | | D41367P | 16 | | | ALL |
| 5014R | 24 | | G2 | GN | 0-0 | 22-22-21 | D41345P | 31 | | | D41367P | 15 | | | ALL |
| 5014Z | | | | GN | 0-0 | 22-22-21 | D41345P | 33 | | | D41367P | 17 | | | ALL |
| 5015B | 24 | | G2 | GO | 22-0 | SPARE | D41345P | 36 | | | D41379P | 25 | | | 115-199 |
| 5015R | 24 | | G2 | GO | 0-0 | SPARE | D41345P | 35 | | | D41379P | 24 | | | 115-199 |
| 5015Z | | | | GO | 0-0 | SPARE | D41345P | 37 | | | D41379P | 26 | | | 115-199 |
| 5016B | 24 | | G2 | GP | 20-0 | 22-24-21 | D41345P | 40 | | | D41367P | 20 | | | ALL |
| 5016R | 24 | | G2 | GP | 0-0 | 22-24-21 | D41345P | 39 | | | D41367P | 19 | | | ALL |
| 5016Z | | | | GP | 0-0 | 22-24-21 | D41345P | 41 | | | D41367P | 21 | | | ALL |
| 5017B | 24 | | G2 | GR | 21-0 | 22-32-12 | D41369P | 35 | | | D41349P | 2 | | | ALL |
| 5017R | 24 | | G2 | GR | 0-0 | 22-32-12 | D41369P | 34 | | | D41349P | 1 | | | ALL |
| 5017Z | | | | GR | 0-0 | 22-32-12 | D41369P | 36 | | | D41349P | 3 | | | ALL |
| 5018B | 24 | | G2 | GS | 25-0 | 22-41-11 | D41345P | 43 | | | D41355P | 18 | | | ALL |
| 5018R | 24 | | G2 | GS | 0-0 | 22-41-11 | D41345P | 42 | | | D41355P | 17 | | | ALL |
| 5018Z | | | | GS | 0-0 | 22-41-11 | D41345P | 45 | | | D41355P | 19 | | | ALL |
| 5019B | 24 | | G2 | GT | 27-0 | 31-31-22 | D41361P | 8 | | | D41369P | 44 | | | 115-199 |
| 5019R | 24 | | G2 | GT | 0-0 | 31-31-22 | D41361P | 9 | | | D41369P | 45 | | | 115-199 |
| 5019Z | | | | GT | 0-0 | 31-31-22 | D41361P | 10 | | | D41369P | 46 | | | 115-199 |
| 5021B | 24 | | G2 | GV | 20-0 | 22-12-21 | D41347P | 6 | | | D41379P | 35 | | | ALL |
| 5021R | 24 | | G2 | GV | 0-0 | 22-12-21 | D41347P | 5 | | | D41379P | 34 | | | ALL |
| 5021Z | | | | GV | 0-0 | 22-12-21 | D41347P | 7 | | | D41379P | 36 | | | ALL |
| 5022B | 24 | | G2 | GW | 26-0 | SPARE | D41369P | 48 | | | D41489P | 16 | | | 115-199 |
| 5022R | 24 | | G2 | GW | 0-0 | SPARE | D41369P | 47 | | | D41489P | 15 | | | 115-199 |
| 5022Z | | | | GW | 0-0 | SPARE | D41369P | 49 | | | D41489P | 17 | | | 115-199 |
| 5023B | 24 | | G2 | GX | 20-0 | 34-12-22 | D41347P | 19 | | | D41377P | 3 | | | ALL |
| 5023R | 24 | | G2 | GX | 0-0 | 34-12-22 | D41347P | 18 | | | D41377P | 2 | | | ALL |
| 5023Z | | | | GX | 0-0 | 34-12-22 | D41347P | 20 | | | D41377P | 4 | | | ALL |
| 5024B | 24 | | G2 | GY | 7-0 | 22-15-11 | D41349P | 8 | | | D41347P | 24 | | | ALL |
| 5024R | 24 | | G2 | GY | 0-0 | 22-15-11 | D41349P | 7 | | | D41347P | 23 | | | ALL |
| 5024Z | | | | GY | 0-0 | 22-15-11 | D41349P | 9 | | | D41347P | 25 | | | ALL |
| 5025B | 24 | | G2 | AE | 18-0 | 31-51-33 | D41907P | 20 | | | D41491P | 47 | | | ALL |
| 5025R | 24 | | G2 | AE | 0-0 | 31-51-33 | D41907P | 19 | | | D41491P | 46 | | | ALL |
| 5025Z | | | | AE | 0-0 | 31-51-33 | D41907P | 21 | | | D41491P | 48 | | | ALL |
| 5026B | 24 | | G2 | HA | 24-0 | 34-55-21 | D41347P | 34 | | | D41355P | 28 | | | ALL |
| 5026R | 24 | | G2 | HA | 0-0 | 34-55-21 | D41347P | 33 | | | D41355P | 27 | | | ALL |
| 5026Z | | | | HA | 0-0 | 34-55-21 | D41347P | 35 | | | D41355P | 29 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 33

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|---------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | | |
| 5027B | 24 | | G2 | HB | 8-0 | 34-61-25 | D41351P | | | 9 | | D41347P | 41 | | | ALL | |
| 5027R | 24 | | G2 | HB | 0-0 | 34-61-25 | D41351P | | | 8 | | D41347P | 40 | | | ALL | |
| 5027Z | | | | HB | 0-0 | 34-61-25 | D41351P | | | 10 | | D41347P | 42 | | | ALL | |
| 5028B | 24 | | G2 | HC | 10-0 | 34-21-21 | D41881P | | | 2 | | D41351P | 12 | | | ALL | |
| 5028R | 24 | | G2 | HC | 0-0 | 34-21-21 | D41881P | | | 1 | | D41351P | 11 | | | ALL | |
| 5028Z | | | | HC | 0-0 | 34-21-21 | D41881P | | | 3 | | D41351P | 13 | | | ALL | |
| 5029B | 24 | | G2 | HD | 10-0 | 34-21-21 | D41881P | | | 5 | | D41351P | 15 | | | ALL | |
| 5029R | 24 | | G2 | HD | 0-0 | 34-21-21 | D41881P | | | 4 | | D41351P | 14 | | | ALL | |
| 5029Z | | | | HD | 0-0 | 34-21-21 | D41881P | | | 6 | | D41351P | 16 | | | ALL | |
| 5030B | 24 | | G2 | HE | 10-0 | 34-61-12 | D41339P | | | 4 | | D41351P | 18 | | | ALL | |
| 5030R | 24 | | G2 | HE | 0-0 | 34-61-12 | D41339P | | | 3 | | D41351P | 17 | | | ALL | |
| 5030Z | | | | HE | 0-0 | 34-61-12 | D41339P | | | 5 | | D41351P | 19 | | | ALL | |
| 5031B | 24 | | G2 | HF | 10-0 | 22-13-21 | D41881P | | | 8 | | D41351P | 21 | | | ALL | |
| 5031R | 24 | | G2 | HF | 0-0 | 22-13-21 | D41881P | | | 7 | | D41351P | 20 | | | ALL | |
| 5031Z | | | | HF | 0-0 | 22-13-21 | D41881P | | | 9 | | D41351P | 22 | | | ALL | |
| 5032B | 24 | | G2 | HG | 7-0 | 22-32-11 | D41349P | | | 11 | | D41351P | 24 | | | ALL | |
| 5032R | 24 | | G2 | HG | 0-0 | 22-32-11 | D41349P | | | 10 | | D41351P | 23 | | | ALL | |
| 5032Z | | | | HG | 0-0 | 22-32-11 | D41349P | | | 12 | | D41351P | 25 | | | ALL | |
| 5033B | 24 | | G2 | HH | 10-0 | 34-61-22 | D41881P | | | 11 | | D41351P | 27 | | | ALL | |
| 5033R | 24 | | G2 | HH | 0-0 | 34-61-22 | D41881P | | | 10 | | D41351P | 26 | | | ALL | |
| 5033Z | | | | HH | 0-0 | 34-61-22 | D41881P | | | 12 | | D41351P | 28 | | | ALL | |
| 5034B | 22 | | GU | HI | 18-0 | 32-42-11 | D41351P | | | 29 | | D41487P | 29 | | | 001-099 | |
| 5034B | 24 | | G2 | HI | 18-0 | 32-42-11 | D41351P | | | 29 | | D41487P | 29 | | | 115-199 | |
| 5034R | 22 | | GU | HI | 0-0 | 32-42-11 | D41351P | | | 30 | | D41487P | 30 | | | 001-099 | |
| 5034R | 24 | | G2 | HI | 0-0 | 32-42-11 | D41351P | | | 30 | | D41487P | 30 | | | 115-199 | |
| 5034Z | | | | HI | 0-0 | 32-42-11 | D41351P | | | 31 | | D41487P | 31 | | | ALL | |
| 5035B | 24 | | G2 | HJ | 24-0 | 22-41-11 | D41347P | | | 44 | | D41355P | 32 | | | ALL | |
| 5035R | 24 | | G2 | HJ | 0-0 | 22-41-11 | D41347P | | | 43 | | D41355P | 31 | | | ALL | |
| 5035Z | | | | HJ | 0-0 | 22-41-11 | D41347P | | | 45 | | D41355P | 33 | | | ALL | |
| 5036B | 24 | | G2 | HK | 10-0 | 34-22-28 | D41881P | | | 14 | | D41351P | 35 | | | ALL | |
| 5036R | 24 | | G2 | HK | 0-0 | 34-22-28 | D41881P | | | 13 | | D41351P | 34 | | | ALL | |
| 5036Z | | | | HK | 0-0 | 34-22-28 | D41881P | | | 15 | | D41351P | 36 | | | ALL | |
| 5037B | 24 | | G2 | HL | 18-0 | SPARE | D41907P | | | 2 | | D41491P | 24 | | | 001-099 | |
| 5037B | 24 | | G2 | HL | 25-0 | SPARE | D41379P | | | 46 | | D41491P | 24 | | | 115-199 | |
| 5037R | 24 | | G2 | HL | 0-0 | SPARE | D41907P | | | 1 | | D41491P | 23 | | | 001-099 | |
| 5037R | 24 | | G2 | HL | 0-0 | SPARE | D41379P | | | 45 | | D41491P | 23 | | | 115-199 | |
| 5037Z | | | | HL | 0-0 | SPARE | D41907P | | | 3 | | D41491P | 25 | | | 001-099 | |
| 5037Z | | | | HL | 0-0 | SPARE | D41379P | | | 47 | | D41491P | 25 | | | 115-199 | |
| 5038B | 24 | | G2 | HM | 22-0 | SPARE | D41345P | | | 49 | | D41369P | 52 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 34

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 5038R | 24 | G2 | HM | | 0-0 | SPARE | D41345P | 38 | | | D41369P | 51 | | | 115-199 |
| 5038Z | | | HM | | 0-0 | SPARE | D41345P | 50 | | | D41369P | 53 | | | 115-199 |
| 5039B | 24 | G2 | HN | | 25-0 | SPARE | D41345P | 54 | | | D41355P | 3 | | | 115-199 |
| 5039R | 24 | G2 | HN | | 0-0 | SPARE | D41345P | 53 | | | D41355P | 2 | | | 115-199 |
| 5039Z | | | HN | | 0-0 | SPARE | D41345P | 55 | | | D41355P | 21 | | | 115-199 |
| 5041B | 24 | G2 | HP | | 17-0 | 34-46-12 | D41491P | 35 | | | D41349P | 18 | | | ALL |
| 5041R | 24 | G2 | HP | | 0-0 | 34-46-12 | D41491P | 34 | | | D41349P | 17 | | | ALL |
| 5041Z | | | HP | | 0-0 | 34-46-12 | D41491P | 36 | | | D41349P | 19 | | | ALL |
| 5042B | 24 | G2 | HR | | 9-0 | 34-25-11 | D41349P | 22 | | | D41881P | 27 | | | 001, 003-099, 115-199 |
| 5042B | 24 | G2 | HR | | 9-0 | SPARE | D41349P | 22 | VP | | D41881P | 27 | | | 002 |
| 5042R | 24 | G2 | HR | | 0-0 | 34-25-11 | D41349P | 21 | | | D41881P | 26 | | | 001, 003-099, 115-199 |
| 5042R | 24 | G2 | HR | | 0-0 | SPARE | D41349P | 21 | VP | | D41881P | 26 | | | 002 |
| 5042Z | | | HR | | 0-0 | 34-25-11 | D41349P | 20 | | | D41881P | 25 | | | 001, 003-099, 115-199 |
| 5042Z | | | HR | | 0-0 | SPARE | D41349P | 20 | | | D41881P | 25 | | | 002 |
| 5043B | 24 | G2 | HS | | 21-0 | 34-25-11 | D41349P | 25 | | | D41867P | 14 | | | 115-199 |
| 5043R | 24 | G2 | HS | | 0-0 | 34-25-11 | D41349P | 24 | | | D41867P | 13 | | | 115-199 |
| 5043Z | | | HS | | 0-0 | 34-25-11 | D41349P | 23 | | | D41867P | 15 | | | 115-199 |
| 5044B | 24 | G2 | HT | | 26-0 | SPARE | D41881P | 34 | | | D41361P | 18 | | | 115-199 |
| 5044R | 24 | G2 | HT | | 0-0 | SPARE | D41881P | 33 | | | D41361P | 17 | | | 115-199 |
| 5044Z | | | HT | | 0-0 | SPARE | D41881P | 32 | | | D41361P | 16 | | | 115-199 |
| 5045B | 24 | G2 | HU | | 26-0 | 31-31-22 | D41881P | 36 | | | D41361P | 20 | | | 115-199 |
| 5045R | 24 | G2 | HU | | 0-0 | 31-31-22 | D41881P | 35 | | | D41361P | 19 | | | 115-199 |
| 5045Z | | | HU | | 0-0 | 31-31-22 | D41881P | 37 | | | D41361P | 21 | | | 115-199 |
| 5046B | 24 | G2 | HV | | 26-0 | 31-31-22 | D41881P | 40 | | | D41361P | 24 | | | 115-199 |
| 5046R | 24 | G2 | HV | | 0-0 | 31-31-22 | D41881P | 39 | | | D41361P | 23 | | | 115-199 |
| 5046Z | | | HV | | 0-0 | 31-31-22 | D41881P | 38 | | | D41361P | 22 | | | 115-199 |
| 5047B | 24 | G2 | KZ | | 26-0 | 31-31-43 | D41881P | 42 | | | D41361P | 26 | | | 001-099 |
| 5047B | 24 | G2 | HW | | 26-0 | 31-31-22 | D41881P | 43 | | | D41361P | 27 | | | 115-199 |
| 5047R | 24 | G2 | KZ | | 0-0 | 31-31-43 | D41881P | 41 | | | D41361P | 25 | | | 001-099 |
| 5047R | 24 | G2 | HW | | 0-0 | 31-31-22 | D41881P | 42 | | | D41361P | 26 | | | 115-199 |
| 5047Z | | | KZ | | 0-0 | 31-31-43 | D41881P | 43 | | | D41361P | 27 | | | 001-099 |
| 5047Z | | | HW | | 0-0 | 31-31-22 | D41881P | 41 | | | D41361P | 25 | | | 115-199 |
| 5048B | 24 | G2 | LC | | 28-0 | 31-31-43 | D41361P | 29 | | | D41883P | 47 | | | 001-099 |
| 5048B | 24 | G2 | HY | | 28-0 | 31-31-22 | D41361P | 29 | | | D41883P | 29 | | | 115-199 |
| 5048R | 24 | G2 | LC | | 0-0 | 31-31-43 | D41361P | 28 | | | D41883P | 46 | | | 001-099 |
| 5048R | 24 | G2 | HY | | 0-0 | 31-31-22 | D41361P | 28 | | | D41883P | 28 | | | 115-199 |
| 5048Z | | | LC | | 0-0 | 31-31-43 | D41361P | 30 | | | D41883P | 48 | | | 001-099 |
| 5048Z | | | HY | | 0-0 | 31-31-22 | D41361P | 30 | | | D41883P | 30 | | | 115-199 |
| 5049B | 24 | G2 | HZ | | 10-0 | 34-22-81 | D41351P | 52 | | | D41881P | 28 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 35

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|-----|--------------------------------------|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 5049B | 24 | | G2 | HZ | 10-0 | 34-22-83 | | D41351P | | | 52 | D41881P | | | 44 | 115-199 |
| 5049R | 24 | | G2 | HZ | 0-0 | 34-22-81 | | D41351P | | | 53 | D41881P | | | 29 | 001-099 |
| 5049R | 24 | | G2 | HZ | 0-0 | 34-22-83 | | D41351P | | | 53 | D41881P | | | 45 | 115-199 |
| 5049Z | | | | HZ | 0-0 | 34-22-81 | | D41351P | | | 54 | D41881P | | | 30 | 001-099 |
| 5049Z | | | | HZ | 0-0 | 34-22-83 | | D41351P | | | 54 | D41881P | | | 46 | 115-199 |
| 5050B | 24 | | G2 | AF | 24-0 | 22-21-11 | | D41351P | | | 42 | D41353P | | | 4 | ALL |
| 5050R | 24 | | G2 | AF | 0-0 | 22-21-11 | | D41351P | | | 41 | D41353P | | | 5 | ALL |
| 5050Z | | | | AF | 0-0 | 22-21-11 | | D41351P | | | 43 | D41353P | | | 6 | ALL |
| 5051B | 24 | | G2 | IB | 8-0 | 21-31-21 | | D41377P | | | 25 | D41883P | | | 21 | ALL |
| 5051R | 24 | | G2 | IB | 0-0 | 21-31-21 | | D41377P | | | 24 | D41883P | | | 20 | ALL |
| 5051Z | | | | IB | 0-0 | 21-31-21 | | D41377P | | | 26 | D41883P | | | 22 | ALL |
| 5052B | 24 | | G2 | IC | 8-0 | SPARE | | D41381P | | | 14 | D41883P | | | 25 | 115-199 |
| 5052R | 24 | | G2 | IC | 0-0 | SPARE | | D41381P | | | 13 | D41883P | | | 26 | 115-199 |
| 5052Z | | | | IC | 0-0 | SPARE | | D41381P | | | 15 | D41883P | | | 27 | 115-199 |
| 5053B | 20 | | QJ | LE | 8-0 | 31-31-44 | | D41361P | | | 45 | D41363P | | | 22 | 001-099 |
| 5053B | 24 | | G2 | ID | 8-0 | 31-31-23 | | D41361P | | | 45 | D41363P | | | 22 | 115-199 |
| 5053R | 20 | | QJ | LE | 0-0 | 31-31-44 | | D41361P | | | 44 | D41363P | | | 21 | 001-099 |
| 5053R | 24 | | G2 | ID | 0-0 | 31-31-23 | | D41361P | | | 44 | D41363P | | | 21 | 115-199 |
| 5053Z | | | | LE | 0-0 | 31-31-44 | | D41361P | | | 46 | D41363P | | | 23 | 001-099 |
| 5053Z | | | | ID | 0-0 | 31-31-23 | | D41361P | | | 46 | D41363P | | | 23 | 115-199 |
| 5063B | 24 | | G2 | AG | 24-0 | 22-24-11 | | D41353P | | | 2 | D41907P | | | 24 | ALL |
| 5063R | 24 | | G2 | AG | 0-0 | 22-24-11 | | D41353P | | | 1 | D41907P | | | 23 | ALL |
| 5063Z | | | | AG | 0-0 | 22-24-11 | | D41353P | | | 3 | D41907P | | | 25 | ALL |
| 5064B | 24 | | G2 | AI | 11-0 | 34-21-21 | | D41001P | | | 2 | D41339P | | | 22 | ALL |
| 5064R | 24 | | G2 | AI | 0-0 | 34-21-21 | | D41001P | | | 1 | D41339P | | | 21 | ALL |
| 5064Z | | | | AI | 0-0 | 34-21-21 | | D41001P | | | 3 | D41339P | | | 23 | ALL |
| 5065B | 24 | | G2 | AJ | 11-0 | SPARE | | D41001P | | | 8 | D41339P | | | 29 | ALL |
| 5065R | 24 | | G2 | AJ | 0-0 | SPARE | | D41001P | | | 7 | D41339P | | | 28 | ALL |
| 5065Z | | | | AJ | 0-0 | SPARE | | D41001P | | | 9 | D41339P | | | 30 | ALL |
| 5066B | 24 | | G2 | AK | 8-0 | 34-22-38 | | D41349P | | | 35 | D41001P | | | 11 | ALL |
| 5066R | 24 | | G2 | AK | 0-0 | 34-22-38 | | D41349P | | | 34 | D41001P | | | 10 | ALL |
| 5066Z | | | | AK | 0-0 | 34-22-38 | | D41349P | | | 36 | D41001P | | | 12 | ALL |
| 5067B | 24 | | G2 | AL | 10-0 | 22-33-11 | | D41349P | | | 48 | D41907P | | | 31 | 001-099 |
| 5067B | 24 | | G2 | AL | 9-0 | 22-33-11 | | D41349P | | | 48 | D41907P | | | 31 | 115-199 |
| 5067R | 24 | | G2 | AL | 0-0 | 22-33-11 | | D41349P | | | 47 | D41907P | | | 30 | ALL |
| 5067Z | | | | AL | 0-0 | 22-33-11 | | D41349P | | | 49 | D41907P | | | 32 | ALL |
| 5068B | 24 | | G2 | AN | 19-0 | 34-61-25 | | D41339P | | | 32 | D41909P | | | 34 | ALL |
| 5068R | 24 | | G2 | AN | 0-0 | 34-61-25 | | D41339P | | | 31 | D41909P | | | 33 | ALL |
| 5068Z | | | | AN | 0-0 | 34-61-25 | | D41339P | | | 33 | D41909P | | | 35 | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 36

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 5069B | 24 | G2 | AO | | 20-0 | 34-61-25 | D41907P | 35 | | | D41909P | 36 | | | ALL |
| 5069R | 24 | G2 | AO | | 0-0 | 34-61-25 | D41907P | 34 | | | D41909P | 37 | | | ALL |
| 5069Z | | | AO | | 0-0 | 34-61-25 | D41907P | 33 | | | D41909P | 38 | | | ALL |
| 5070B | 24 | G2 | AP | | 20-0 | 34-61-25 | D41907P | 36 | | | D41909P | 40 | | | ALL |
| 5070R | 24 | G2 | AP | | 0-0 | 34-61-25 | D41907P | 37 | | | D41909P | 39 | | | ALL |
| 5070Z | | | AP | | 0-0 | 34-61-25 | D41907P | 38 | | | D41909P | 41 | | | ALL |
| 5071B | 24 | G2 | AQ | | 21-0 | 22-33-11 | D41349P | 52 | | | D41867P | 40 | | | 001, 003-099 |
| 5071B | 24 | G2 | AQ | | 10-0 | 22-33-11 | D41349P | 52 | | | D41867P | 40 | | | 002 |
| 5071B | 24 | G2 | AS | | 21-0 | 22-33-11 | D41349P | 52 | | | D41867P | 40 | | | 115-199 |
| 5071R | 24 | G2 | AQ | | 0-0 | 22-33-11 | D41349P | 51 | | | D41867P | 39 | | | 001-099 |
| 5071R | 24 | G2 | AS | | 0-0 | 22-33-11 | D41349P | 51 | | | D41867P | 39 | | | 115-199 |
| 5071Z | | | AQ | | 0-0 | 22-33-11 | D41349P | 50 | | | D41867P | 38 | | | 001-099 |
| 5071Z | | | AS | | 0-0 | 22-33-11 | D41349P | 50 | | | D41867P | 38 | | | 115-199 |
| 5072B | 24 | G2 | AV | | 20-0 | 28-41-11 | D41867P | 47 | | | D05660 | 2 | | | 001-099 |
| 5072B | 24 | G2 | AV | | 25-0 | 28-41-11 | D41867P | 47 | | | D05660 | 2 | | | 115-199 |
| 5072R | 24 | G2 | AV | | 0-0 | 28-41-11 | D41867P | 48 | | | D05660 | 1 | | | ALL |
| 5072Z | | | AV | | 0-0 | 28-41-11 | D41867P | 49 | | | GD02542 | ST.. | E | | ALL |
| 5075B | 24 | G2 | AS | | 8-0 | SPARE | D41001P | 14 | | | D41349P | 5 | | | 001, 003-099 |
| 5075B | 24 | G2 | AS | | 8-0 | SPARE | D41001P | 14 | | | D41349P | REF | VP | | 002 |
| 5075R | 24 | G2 | AS | | 0-0 | SPARE | D41001P | 13 | | | D41349P | 4 | | | 001, 003-099 |
| 5075R | 24 | G2 | AS | | 0-0 | SPARE | D41001P | 13 | | | D41349P | REF | VP | | 002 |
| 5075Z | | | AS | | 0-0 | SPARE | D41001P | 15 | | | D41349P | 6 | | | 001, 003-099 |
| 5075Z | | | AS | | 0-0 | SPARE | D41001P | 15 | | | D41349P | REF | VP | | 002 |
| 5078B | 24 | G2 | AW | | 8-0 | 27-58-31 | D01251 | 2 | | | D41379P | 17 | | | ALL |
| 5078R | 24 | G2 | AW | | 0-0 | 27-58-31 | D01251 | 1 | | | D41379P | 18 | | | ALL |
| 5078Z | | | AW | | 0-0 | 27-58-31 | D01251 | 3 | | | D41379P | 21 | | | ALL |
| 5079B | 24 | G2 | KV | | 17-0 | 27-32-21 | D41345P | 54 | | | D41491P | 52 | | | 001-099 |
| 5079R | 24 | G2 | KV | | 0-0 | 27-32-21 | D41345P | 53 | | | D41491P | 51 | | | 001-099 |
| 5079Z | | | KV | | 0-0 | 27-32-21 | D41345P | 55 | | | D41491P | 31 | | | 001-099 |
| 5080B | 24 | G2 | KA | | 23-0 | 34-22-29 | D43005P | 10 | | | D43007P | 10 | | | 001-099 |
| 5080R | 24 | G2 | KA | | 0-0 | 34-22-29 | D43005P | 9 | | | D43007P | 9 | | | 001-099 |
| 5080Z | | | KA | | 0-0 | 34-22-29 | D43005P | 11 | | | D43007P | 11 | | | 001-099 |
| 5081B | 24 | G2 | KB | | 23-0 | 34-51-21 | D43007P | 3 | | | D43005P | 3 | | | 001-099 |
| 5081R | 24 | G2 | KB | | 0-0 | 34-51-21 | D43007P | 2 | | | D43005P | 2 | | | 001-099 |
| 5081Z | | | KB | | 0-0 | 34-51-21 | D43007P | 4 | | | D43005P | 4 | | | 001-099 |
| 5082B | 24 | G2 | KC | | 23-0 | 34-51-21 | D43007P | 6 | | | D43005P | 6 | | | 001-099 |
| 5082R | 24 | G2 | KC | | 0-0 | 34-51-21 | D43007P | 5 | | | D43005P | 5 | | | 001-099 |
| 5082Z | | | KC | | 0-0 | 34-51-21 | D43007P | 7 | | | D43005P | 7 | | | 001-099 |
| 5083B | 24 | G2 | KD | | 25-0 | 23-51-13 | D41371P | 54 | | | D43005P | 13 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 37

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--------------------------------------|-------------|---------|-------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 5083R | 24 | G2 | KD | 0-0 | 23-51-13 | D41371P | 53 | | | | D43005P | 12 | | | 001-099 |
| 5083Z | | | KD | 0-0 | 23-51-13 | D41371P | 55 | | | | D43005P | 14 | | | 001-099 |
| 5084B | 24 | G2 | KE | 27-0 | 23-51-14 | D41371P | 45 | | | | D41355P | 41 | | | 001-099 |
| 5084R | 24 | G2 | KE | 0-0 | 23-51-14 | D41371P | 44 | | | | D41355P | 40 | | | 001-099 |
| 5084Z | | | KE | 0-0 | 23-51-14 | D41371P | 46 | | | | D41355P | 42 | | | 001-099 |
| 5085B | 24 | G2 | KF | 27-0 | 23-51-14 | D41371P | 48 | | | | D41355P | 44 | | | 001-099 |
| 5085R | 24 | G2 | KF | 0-0 | 23-51-14 | D41371P | 47 | | | | D41355P | 43 | | | 001-099 |
| 5085Z | | | KF | 0-0 | 23-51-14 | D41371P | 49 | | | | D41355P | 45 | | | 001-099 |
| 5086B | 24 | G2 | KG | 27-0 | 23-51-12 | D41371P | 51 | | | | D41355P | 51 | | | 001-099 |
| 5086R | 24 | G2 | KG | 0-0 | 23-51-12 | D41371P | 50 | | | | D41355P | 50 | | | 001-099 |
| 5086Z | | | KG | 0-0 | 23-51-12 | D41371P | 52 | | | | D41355P | 52 | | | 001-099 |
| 5087B | 24 | G2 | KH | 23-0 | SPARE | D43007P | 13 | | | | D43005P | 18 | | | 001-099 |
| 5087R | 24 | G2 | KH | 0-0 | SPARE | D43007P | 12 | | | | D43005P | 17 | | | 001-099 |
| 5087Z | | | KH | 0-0 | SPARE | D43007P | 14 | | | | D43005P | 19 | | | 001-099 |
| 5091B | 24 | G2 | KL | 17-0 | 34-46-12 | D41349P | 54 | | | | D41491P | 54 | | | ALL |
| 5091R | 24 | G2 | KL | 0-0 | 34-46-12 | D41349P | 53 | | | | D41491P | 53 | | | ALL |
| 5091Z | | | KL | 0-0 | 34-46-12 | D41349P | 55 | | | | D41491P | 55 | | | ALL |
| 5092B | 24 | G2 | KM | 26-0 | 27-32-21 | D41883P | 42 | | | | D41491P | 43 | | | 001-099 |
| 5092B | 24 | G2 | KM | 22-0 | 27-32-21 | D41909P | 51 | | | | D41491P | 51 | | | 115-199 |
| 5092R | 24 | G2 | KM | 0-0 | 27-32-21 | D41883P | 41 | | | | D41491P | 42 | | | 001-099 |
| 5092R | 24 | G2 | KM | 0-0 | 27-32-21 | D41909P | 50 | | | | D41491P | 50 | | | 115-199 |
| 5092Z | | | KM | 0-0 | 27-32-21 | D41883P | 43 | | | | D41491P | 44 | | | 001-099 |
| 5092Z | | | KM | 0-0 | 27-32-21 | D41909P | 52 | | | | D41491P | 52 | | | 115-199 |
| 5093B | 24 | G2 | KN | 25-0 | SPARE | D41339P | 38 | | | | D41355P | 47 | | | 115-199 |
| 5093R | 24 | G2 | KN | 0-0 | SPARE | D41339P | 37 | | | | D41355P | 46 | | | 115-199 |
| 5093Z | | | KN | 0-0 | SPARE | D41339P | 36 | | | | D41355P | 48 | | | 115-199 |
| 5094B | 24 | G2 | KO | 26-0 | SPARE | D41881P | 29 | | | | D41355P | 54 | | | 115-199 |
| 5094R | 24 | G2 | KO | 0-0 | SPARE | D41881P | 28 | | | | D41355P | 53 | | | 115-199 |
| 5094Z | | | KO | 0-0 | SPARE | D41881P | 30 | | | | D41355P | 55 | | | 115-199 |
| 5101B | 22 | X2 | FA | 18-0 | 34-61-26 | D43017P | 4 | | | | D43021P | 4 | | | 115-199 |
| 5101R | 22 | X2 | FA | 0-0 | 34-61-26 | D43017P | 3 | | | | D43021P | 3 | | | 115-199 |
| 5101Z | | | FA | 0-0 | 34-61-26 | D43017P | 5 | | | | D43021P | 5 | | | 115-199 |
| 5102B | 22 | X2 | FB | 18-0 | 34-61-26 | D43017P | 7 | | | | D43021P | 7 | | | 115-199 |
| 5102R | 22 | X2 | FB | 0-0 | 34-61-26 | D43017P | 6 | | | | D43021P | 6 | | | 115-199 |
| 5102Z | | | FB | 0-0 | 34-61-26 | D43017P | 8 | | | | D43021P | 8 | | | 115-199 |
| 5103B | 22 | X2 | FC | 19-0 | 34-61-26 | D43017P | 10 | | | | D42173P | 2 | | | 115-199 |
| 5103R | 22 | X2 | FC | 0-0 | 34-61-26 | D43017P | 9 | | | | D42173P | 1 | | | 115-199 |
| 5103Z | | | FC | 0-0 | 34-61-26 | D43017P | 11 | | | | D42173P | 3 | | | 115-199 |
| 5104B | 22 | X2 | FD | 18-0 | 34-61-26 | D43017P | 13 | | | | D42173P | 5 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 38

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | |
| 5104R | 22 | X2 | FD | | 0-0 | 34-61-26 | D43017P | 12 | | | D42173P | 4 | | | 115-199 |
| 5104Z | | | FD | | 0-0 | 34-61-26 | D43017P | 14 | | | D42173P | 6 | | | 115-199 |
| 5105B | 22 | X2 | FE | | 18-0 | 34-61-26 | D43017P | 16 | | | D43021P | 16 | | | 115-199 |
| 5105R | 22 | X2 | FE | | 0-0 | 34-61-26 | D43017P | 15 | | | D43021P | 15 | | | 115-199 |
| 5105Z | | | FE | | 0-0 | 34-61-26 | D43017P | 17 | | | D43021P | 17 | | | 115-199 |
| 5115B | 24 | G2 | DF | | 8-0 | 34-45-01 | D41339P | 40 | | | D41347P | 47 | | | ALL |
| 5115R | 24 | G2 | DF | | 0-0 | 34-45-01 | D41339P | 39 | | | D41347P | 46 | | | ALL |
| 5115Z | | | DF | | 0-0 | 34-45-01 | D41339P | 41 | | | D41347P | 49 | | | ALL |
| 5116B | 24 | G2 | DG | | 23-0 | 34-45-02 | D43005P | 27 | | | D41339P | 43 | | | 001-099 |
| 5116B | 24 | G2 | DG | | 23-0 | 34-45-02 | D43005P | 2 | | | D41339P | 7 | | | 115-199 |
| 5116R | 24 | G2 | DG | | 0-0 | 34-45-02 | D43005P | 26 | | | D41339P | 42 | | | 001-099 |
| 5116R | 24 | G2 | DG | | 0-0 | 34-45-02 | D43005P | 1 | | | D41339P | 6 | | | 115-199 |
| 5116Z | | | DG | | 0-0 | 34-45-02 | D43005P | 28 | | | D41339P | 44 | | | 001-099 |
| 5116Z | | | DG | | 0-0 | 34-45-02 | D43005P | 3 | | | D41339P | 8 | | | 115-199 |
| 5117B | 24 | G2 | DH | | 23-0 | 34-45-02 | D43005P | 30 | | | D41339P | 46 | | | 001-099 |
| 5117B | 24 | G2 | KH | | 23-0 | 34-45-02 | D43005P | 5 | | | D41339P | 10 | | | 115-199 |
| 5117R | 24 | G2 | DH | | 0-0 | 34-45-02 | D43005P | 29 | | | D41339P | 45 | | | 001-099 |
| 5117R | 24 | G2 | KH | | 0-0 | 34-45-02 | D43005P | 4 | | | D41339P | 9 | | | 115-199 |
| 5117Z | | | DH | | 0-0 | 34-45-02 | D43005P | 31 | | | D41339P | 47 | | | 001-099 |
| 5117Z | | | KH | | 0-0 | 34-45-02 | D43005P | 6 | | | D41339P | 11 | | | 115-199 |
| 5118B | 24 | G2 | DI | | 22-0 | 34-45-02 | D41379P | 46 | | | D41339P | 49 | | | 001-099 |
| 5118R | 24 | G2 | DI | | 0-0 | 34-45-02 | D41379P | 45 | | | D41339P | 48 | | | 001-099 |
| 5118Z | | | DI | | 0-0 | 34-45-02 | D41379P | 47 | | | D41339P | 50 | | | 001-099 |
| 5119B | 24 | G2 | DJ | | 23-0 | 34-45-02 | D41339P | 52 | | | D41883P | 8 | | | 001-099 |
| 5119B | 24 | G2 | KJ | | 23-0 | 34-45-02 | D41339P | 52 | | | D41883P | 8 | | | 115-199 |
| 5119R | 24 | G2 | DJ | | 0-0 | 34-45-02 | D41339P | 51 | | | D41883P | 7 | | | 001-099 |
| 5119R | 24 | G2 | KJ | | 0-0 | 34-45-02 | D41339P | 51 | | | D41883P | 7 | | | 115-199 |
| 5119Z | | | DJ | | 0-0 | 34-45-02 | D41339P | 53 | | | D41883P | 10 | | | 001-099 |
| 5119Z | | | KJ | | 0-0 | 34-45-02 | D41339P | 53 | | | D41883P | 10 | | | 115-199 |
| 5120B | 24 | G2 | KP | | 23-0 | SPARE | D43005P | 10 | | | D41339P | 43 | | | 115-199 |
| 5120R | 24 | G2 | KP | | 0-0 | SPARE | D43005P | 9 | | | D41339P | 42 | | | 115-199 |
| 5120Z | | | KP | | 0-0 | SPARE | D43005P | 11 | | | D41339P | 44 | | | 115-199 |
| 5122B | 22 | X2 | FV | | 19-0 | 34-61-26 | D43017P | 24 | | | D42173P | 8 | | | 115-199 |
| 5122R | 22 | X2 | FV | | 0-0 | 34-61-26 | D43017P | 23 | | | D42173P | 7 | | | 115-199 |
| 5122Z | | | FV | | 0-0 | 34-61-26 | D43017P | 25 | | | D42173P | 9 | | | 115-199 |
| 5123B | 22 | X2 | FW | | 18-0 | 34-61-26 | D43017P | 27 | | | D43021P | 27 | | | 115-199 |
| 5123R | 22 | X2 | FW | | 0-0 | 34-61-26 | D43017P | 26 | | | D43021P | 26 | | | 115-199 |
| 5123Z | | | FW | | 0-0 | 34-61-26 | D43017P | 28 | | | D43021P | 28 | | | 115-199 |
| 5125B | 22 | GU | LF | | 8-0 | 31-31-63 | D41361P | 50 | | | D41363P | 24 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 39

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | |
|------------------------|-------------|----|----|--------------------------------------|-------------|----------|---------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4473 | 286N4473 | | | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | | |
| 5125R | 22 | GU | LF | | 0-0 | 31-31-63 | | D41361P | 49 | | | D41363P | 19 | | | 001-099 |
| 5125Z | | | LF | | 0-0 | 31-31-63 | | D41361P | 51 | | | D41363P | 5 | | | 001-099 |
| 5130B | 24 | G2 | KX | | 19-0 | 31-31-42 | | D41345P | 36 | | | D41909P | 47 | | | 001-099 |
| 5130R | 24 | G2 | KX | | 0-0 | 31-31-42 | | D41345P | 35 | | | D41909P | 46 | | | 001-099 |
| 5130Z | | | KX | | 0-0 | 31-31-42 | | D41345P | 37 | | | D41909P | 48 | | | 001-099 |
| 5131B | 24 | G2 | KY | | 25-0 | 31-31-42 | | D41345P | 50 | | | D41361P | 53 | | | 001-099 |
| 5131R | 24 | G2 | KY | | 0-0 | 31-31-42 | | D41345P | 49 | | | D41361P | 52 | | | 001-099 |
| 5131Z | | | KY | | 0-0 | 31-31-42 | | D41345P | 38 | | | D41361P | 54 | | | 001-099 |
| 5132B | 24 | G2 | LD | | 25-0 | 31-31-43 | | D41361P | 18 | | | D43007P | 20 | | | 001-099 |
| 5132B | 24 | G2 | LD | | 25-0 | SPARE | | D41361P | 18 | | | D43007P | 20 | | | 010-099 |
| 5132R | 24 | G2 | LD | | 0-0 | 31-31-43 | | D41361P | 17 | | | D43007P | 19 | | | 001-009 |
| 5132R | 24 | G2 | LD | | 0-0 | SPARE | | D41361P | 17 | | | D43007P | 19 | | | 010-099 |
| 5132Z | | | LD | | 0-0 | 31-31-43 | | D41361P | 19 | | | D43007P | 21 | | | 001-009 |
| 5132Z | | | LD | | 0-0 | SPARE | | D41361P | 19 | | | D43007P | 21 | | | 010-099 |
| 5133B | 24 | G2 | LA | | 26-0 | 31-31-43 | | D41881P | 33 | | | D41361P | 37 | | | 001-099 |
| 5133R | 24 | G2 | LA | | 0-0 | 31-31-43 | | D41881P | 32 | | | D41361P | 36 | | | 001-099 |
| 5133Z | | | LA | | 0-0 | 31-31-43 | | D41881P | 34 | | | D41361P | 38 | | | 001-099 |
| 5134B | 24 | G2 | LB | | 26-0 | 31-31-43 | | D41881P | 36 | | | D41361P | 22 | | | 001-099 |
| 5134R | 24 | G2 | LB | | 0-0 | 31-31-43 | | D41881P | 35 | | | D41361P | 21 | | | 001-099 |
| 5134Z | | | LB | | 0-0 | 31-31-43 | | D41881P | 37 | | | D41361P | 23 | | | 001-099 |
| 5172B | 22 | GU | BF | | 11-0 | 34-58-11 | | D41907P | 7 | | | D41349P | 5 | | | 115-199 |
| 5172R | 22 | GU | BF | | 0-0 | 34-58-11 | | D41907P | 6 | | | D41349P | 4 | | | 115-199 |
| 5172Z | | | BF | | 0-0 | 34-58-11 | | D41907P | 8 | | | D41349P | 6 | | | 115-199 |
| 5189B | 22 | GU | JY | | 30-0 | 34-46-12 | | D41349P | 5 | | | D41883P | 35 | | | 002 |
| 5189R | 22 | GU | JY | | 0-0 | 34-46-12 | | D41349P | 4 | | | D41883P | 34 | | | 002 |
| 5189Z | | | JY | | 0-0 | 34-46-12 | | D41883P | 36 | | | D41349P | 6 | | | 002 |
| 5194B | 22 | GU | BG | | 12-2 | 34-58-21 | | D41881P | 51 | | | D41001P | 5 | | | 115-199 |
| 5194R | 22 | GU | BG | | 0-0 | 34-58-21 | | D41881P | 50 | | | D41001P | 4 | | | 115-199 |
| 5194Z | | | BG | | 0-0 | 34-58-21 | | D41881P | 55 | | | D41001P | 6 | | | 115-199 |
| 5240B | 22 | GU | IN | | 10-0 | 34-46-12 | | D41351P | 45 | | | D41349P | 15 | | | 002 |
| 5240R | 22 | GU | IN | | 0-0 | 34-46-12 | | D41351P | 44 | | | D41349P | 14 | | | 002 |
| 5240Z | | | IN | | 0-0 | 34-46-12 | | D41351P | 46 | | | D41349P | 16 | | | 002 |
| 5242B | 22 | GU | MZ | | 10-0 | 34-46-12 | | D41881P | 49 | | | D41349P | 27 | | | 002 |
| 5242R | 22 | GU | MZ | | 0-0 | 34-46-12 | | D41881P | 48 | | | D41349P | 26 | | | 002 |
| 5242Z | | | MZ | | 0-0 | 34-46-12 | | D41881P | 47 | | | D41349P | 28 | | | 002 |
| 5256B | 22 | GU | AT | | 15-3 | 31-31-41 | | D41487P | 17 | | | D43021P | 21 | | | 010-099 |
| 5256R | 22 | GU | AT | | 0-0 | 31-31-41 | | D41487P | 15 | | | D43021P | 20 | | | 010-099 |
| 5256Z | | | AT | | 0-0 | 31-31-41 | | D41487P | 18 | | | D43021P | 22 | | | 010-099 |
| 5257B | 22 | GU | BM | | 26-2 | 31-31-41 | | D41909P | 50 | | | D43315P | 2 | | | 010-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 40

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity |
|------------------------|-------------|--------------------------------------|----|------|-------------|---------|-------|------|------|---------|-------|------|------|-----------------------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4473 | 286N4473 | E/E RACK,INTERRACK RIGHT (continued) | | | | | | | | | | | | | |
| 5257R | 22 | GU | BM | 0-0 | 31-31-41 | D41909P | 49 | | | D43315P | 1 | | | 010-099 | |
| 5257Z | | | BM | 0-0 | 31-31-41 | D41909P | 51 | | | D43315P | 3 | | | 010-099 | |
| 8071B | 22 | GU | JZ | 10-0 | 34-46-12 | D41349P | 46 | | | D41881P | 52 | | | 002 | |
| 8071R | 22 | GU | JZ | 0-0 | 34-46-12 | D41349P | 33 | | | D41881P | 51 | | | 002 | |
| 8071Z | | | JZ | 0-0 | 34-46-12 | D41349P | 29 | | | D41881P | 50 | | | 002 | |
| A-AA | | | BI | 0-0 | 23-41-12 | SM00001 | | 9 | | D00423 | RED | | | ALL | |
| A-AB | | | BI | 0-0 | 23-41-12 | SM00002 | | 9 | | D00423 | BLU | | | ALL | |
| A-AC | | | BI | 0-0 | 23-41-12 | SM00003 | | 9 | | D00423 | BLK | | | ALL | |
| B-AA | | | BK | 0-0 | 23-41-12 | SM00004 | | 9 | | D00843 | RED | | | ALL | |
| B-AB | | | BK | 0-0 | 23-41-12 | SM00005 | | 9 | | D00843 | BLU | | | ALL | |
| B-AC | | | BK | 0-0 | 23-41-12 | SM00006 | | 9 | | D00843 | BLK | | | ALL | |
| W4475 | 286N4475 | E/E RACK,INTERRACK CENTER | | | | | | | | | | | | | |
| 0001 | 22 | GA | | 22-0 | 34-21-31 | D41409P | 1 | | | D41397P | 7 | | | ALL | |
| 0002 | 22 | GA | | 22-0 | 34-21-31 | D41409P | 2 | | | D41397P | 8 | | | ALL | |
| 0003 | 22 | GA | | 22-0 | 34-21-31 | D41409P | 3 | | | D41397P | 9 | | | ALL | |
| 0004 | 24 | GK | | 12-0 | 31-51-34 | D41815P | 37 | | | D41599P | 4 | | | 115-199 | |
| 0005 | 22 | GA | | 23-0 | 22-12-31 | D41395P | 11 | | | D41419P | 7 | | | ALL | |
| 0006 | 22 | GA | | 23-0 | 22-12-31 | D41395P | 18 | | | D41419P | 1 | | | ALL | |
| 0007 | 22 | GA | | 23-0 | 22-12-31 | D41395P | 19 | | | D41419P | 2 | | | ALL | |
| 0008 | 22 | GA | | 12-0 | 22-12-31 | D41395P | 20 | | | D41675P | 3 | | | ALL | |
| 0009 | 22 | GA | | 12-0 | 22-12-31 | D41395P | 21 | | | D41675P | 4 | | | ALL | |
| 0011 | 22 | GA | | 14-0 | SPARE | D41493P | 1 | | | D41391P | 13 | | | 115-199 | |
| 0012 | 22 | GA | | 12-0 | SPARE | D41393P | 12 | | | D41395P | 28 | | | 001, 003-099, 115-199 | |
| 0012 | 22 | GA | | 12-0 | SPARE | D41393P | 12 | | | D41395P | REF | JB | | 002 | |
| 0013 | 22 | GA | | 12-0 | 22-14-31 | D41393P | 13 | | | D41395P | 29 | | | ALL | |
| 0014 | 22 | GA | | 12-0 | SPARE | D41393P | 14 | | | D41395P | 30 | | | ALL | |
| 0015 | 22 | GA | | 12-0 | 22-14-31 | D41393P | 15 | | | D41395P | 31 | | | ALL | |
| 0016 | 22 | GA | | 12-0 | 22-14-31 | D41393P | 16 | | | D41395P | 32 | | | ALL | |
| 0017 | 22 | GA | | 10-0 | 22-14-31 | D41391P | 14 | | | D41395P | 33 | | | ALL | |
| 0018 | 22 | GA | | 10-0 | SPARE | D41391P | 15 | | | D41395P | 34 | | | 115-199 | |
| 0019 | 22 | GA | | 10-0 | 22-14-31 | D41391P | 16 | | | D41395P | 35 | | | ALL | |
| 0020 | 22 | GA | | 10-0 | 22-14-31 | D41391P | 17 | | | D41395P | 36 | | | ALL | |
| 0021 | 22 | GA | | 10-0 | SPARE | D41391P | 18 | | | D41395P | 37 | | | ALL | |
| 0022 | 22 | GA | | 10-0 | 22-15-12 | D41395P | 44 | | | D41391P | 22 | | | ALL | |
| 0023 | 22 | GA | | 12-0 | 22-15-12 | D41395P | 45 | | | D41393P | 17 | | | ALL | |
| 0024 | 22 | GA | | 10-0 | SPARE | D41395P | 46 | | | D41391P | 23 | | | 115-199 | |
| 0025 | 22 | GA | | 10-0 | SPARE | D41395P | 47 | | | D41391P | 24 | | | 115-199 | |
| 0026 | 22 | GA | | 12-0 | SPARE | D41395P | 48 | | | D41393P | 22 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 41

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4475 | 286N4475 | | | E/E RACK,INTERRACK CENTER (continued) | | | | | | | | | | | |
| 0027 | 22 | | GA | | 12-0 | SPARE | D41395P | | 49 | | D41393P | 23 | | | 115-199 |
| 0028 | 22 | | GA | | 22-0 | 22-22-11 | D41815P | | 1 | | D41399P | 1 | | | ALL |
| 0029 | 22 | | GA | | 22-0 | 22-22-11 | D41815P | | 2 | | D41399P | 2 | | | ALL |
| 0030 | 22 | | GA | | 22-0 | 22-22-11 | D41815P | | 6 | | D41399P | 6 | | | ALL |
| 0031 | 22 | | GA | | 23-0 | SPARE | D41675P | | 5 | | D41399P | 7 | | | 115-199 |
| 0032 | 22 | | GA | | 23-0 | 22-21-11 | D41397P | | 16 | | D41399P | 11 | | | ALL |
| 0033 | 22 | | GA | | 23-0 | 27-09-13 | D41409P | | 5 | | D41399P | 17 | | | ALL |
| 0034 | 22 | | GA | | 23-0 | 27-09-13 | D41409P | | 6 | | D41399P | 16 | | | ALL |
| 0035 | 22 | | GA | | 17-0 | 27-09-12 | D41493P | | 8 | | D41495P | 6 | | | ALL |
| 0036 | 22 | | GA | | 21-0 | 27-09-12 | D41495P | | 5 | | D41399P | 18 | | | ALL |
| 0037 | 24 | | GK | | 18-0 | 34-31-31 | D41493P | | 2 | | D41395P | 50 | | | ALL |
| 0038 | 24 | | GK | | 23-0 | 34-33-31 | D41419P | | 11 | | D41395P | 51 | | | ALL |
| 0039 | 24 | | GK | | 23-0 | 34-33-31 | D41419P | | 12 | | D41495P | 7 | | | ALL |
| 0040 | 24 | | GK | | 17-0 | 27-58-31 | D41419P | | 13 | | D41409P | 4 | | | ALL |
| 0041 | 22 | | GA | | 12-0 | 22-14-31 | D41393P | | 24 | | D41395P | 52 | | | ALL |
| 0042 | 22 | | GA | | 18-0 | 22-14-31 | D41409P | | 12 | | D41391P | 46 | | | ALL |
| 0043 | 20 | | GA | | 11-0 | 34-21-31 | D41815P | | 11 | | D41397P | 20 | | | ALL |
| 0046 | 22 | | GA | | 2-0 | 27-09-12 | D41399P | | 27 | | D40105P | 1 | VG | | ALL |
| 0047 | 22 | | GA | | 23-0 | SPARE | D41409P | | 7 | | D41399P | 24 | | | 001-099 |
| 0048 | 22 | | GA | | 10-0 | 22-11-32 | D41815P | | 10 | | D41391P | 32 | | | 001-099 |
| 0048 | 22 | | GA | | 10-0 | 22-11-32 | D41391P | | 32 | | D41815P | 10 | | | 115-199 |
| 0050 | 22 | | GA | | 14-0 | SPARE | D41391P | | 28 | | D41493P | 3 | | | 115-199 |
| 0051 | 22 | | GA | | 22-0 | SPARE | D41397P | | 30 | | D41409P | 8 | | | 115-199 |
| 0052 | 22 | | GA | | 22-0 | SPARE | D41409P | | 52 | | D41397P | 34 | | | 115-199 |
| 0053 | 24 | | GK | | 17-0 | 27-58-31 | D41409P | | 10 | | D41419P | 14 | | | ALL |
| 0054 | 24 | | GK | | 21-0 | SPARE | D41409P | | 11 | | D41815P | 18 | | | 115-199 |
| 0055 | 24 | | GK | | 23-0 | SPARE | D41419P | | 15 | | D41495P | 11 | | | 115-199 |
| 0056 | 22 | | GA | | 20-0 | SPARE | D41493P | | 6 | | D41399P | 22 | | | 115-199 |
| 0057 | 22 | | GA | | 17-0 | SPARE | D41493P | | 7 | | D41495P | 12 | | | ALL |
| 0058 | 22 | | GA | | 12-0 | SPARE | D41495P | | 13 | | D41393P | 32 | | | 115-199 |
| 0059 | 22 | | GA | | 21-0 | SPARE | D41495P | | 14 | | D41399P | 23 | | | 115-199 |
| 0060 | 22 | | GA | | 23-0 | SPARE | D41675P | | 6 | | D41399P | 24 | | | 115-199 |
| 0062 | 22 | | GA | | 19-0 | SPARE | D41675P | | 5 | | D41493P | 4 | | | 001-099 |
| 0063 | 22 | | GA | | 25-0 | 22-24-11 | D41419P | | 3 | | D41399P | 25 | | | ALL |
| 0064 | 22 | | GA | | 14-0 | 76-11-21 | D41493P | | 9 | | D41419P | 19 | | | ALL |
| 0065 | 24 | | GK | | 9-0 | 31-31-62 | D41399P | | 15 | | D41403P | 16 | | | 001-099 |
| 0066 | 22 | | GA | | 10-0 | 22-15-12 | D41391P | | 36 | | D41815P | 31 | | | ALL |
| 0067 | 22 | | GA | | 12-0 | 22-15-12 | D41815P | | 32 | | D41393P | 40 | | | ALL |
| 0071 | 22 | | GA | | 17-0 | 27-09-12 | D41495P | | 15 | | D41493P | 17 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 42

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4475 | 286N4475 | | | E/E RACK,INTERRACK CENTER (continued) | | | | | | | | | | | |
| 0072 | 22 | | GA | | 17-0 | 27-09-12 | D41495P | | 16 | | D41493P | 15 | | | ALL |
| 0073 | 22 | | GA | | 17-0 | 27-09-12 | D41495P | | 17 | | D41493P | 13 | | | ALL |
| 0074 | 22 | | GA | | 20-0 | 27-09-12 | D41493P | | 18 | | D41399P | 26 | | | ALL |
| 0075 | 22 | | GA | | 20-0 | 27-09-12 | D41493P | | 16 | | D40105J | 1 | VY | | ALL |
| 0076 | 22 | | GA | | 20-0 | 27-09-12 | D41399P | | 28 | | D41493P | 14 | | | ALL |
| 0077 | 22 | | GA | | 14-0 | 27-48-21 | D41419P | | 20 | | D41493P | 19 | | | ALL |
| 0078 | 22 | | GA | | 19-0 | 27-48-21 | D41493P | | 20 | | D41675P | 7 | | | ALL |
| 0079 | 22 | | GA | | 10-0 | 22-14-11 | D41395P | | 10 | | D41391P | 40 | | | ALL |
| 0080 | 22 | | GA | | 12-0 | 22-14-21 | D41815P | | 39 | | D41393P | 11 | | | ALL |
| 0081 | 22 | | GA | | 11-0 | 22-14-21 | D41391P | | 41 | | D41393P | 36 | | | ALL |
| 0082 | 22 | | GA | | 11-0 | 22-14-21 | D41391P | | 42 | | D41393P | 37 | | | ALL |
| 0084 | 22 | | GA | | 10-0 | 22-14-11 | D41815P | | 38 | | D41391P | 47 | | | ALL |
| 0086 | 24 | | GK | | 10-0 | 34-45-01 | D41815P | | 12 | | D41391P | 51 | | | ALL |
| 0087 | 24 | | GK | | 10-0 | 34-45-01 | D41815P | | 13 | | D41391P | 52 | | | ALL |
| 0088 | 24 | | GK | | 10-0 | 34-45-01 | D41815P | | 14 | | D41391P | 53 | | | ALL |
| 0089 | 24 | | GK | | 9-0 | 31-31-62 | D41399P | | 31 | | D41403P | 17 | | | 001-099 |
| 0122 | 20 | | GA | | 10-0 | 28-22-11 | S10711 | | 1C | Z2 | GD00262 | DC.. | E | | ALL |
| 0123 | 22 | | GA | | 10-0 | 28-22-11 | S10711 | | 1NO | Z2 | D41495P | 30 | | | ALL |
| 0201 | 22 | | PA | | 18-0 | 34-22-38 | D41493P | | 21 | | D41815P | 48 | | | 115-199 |
| 2001B | 22 | | GB | AR | 22-0 | 22-12-31 | D41815P | | 41 | | D41399P | 30 | | | ALL |
| 2001R | 22 | | GB | AR | 0-0 | 22-12-31 | D41815P | | 40 | | D41399P | 29 | | | ALL |
| 5001B | 24 | | G2 | AA | 13-0 | 34-22-28 | D41393P | | 2 | | D41397P | 2 | | | ALL |
| 5001R | 24 | | G2 | AA | 0-0 | 34-22-28 | D41393P | | 1 | | D41397P | 1 | | | ALL |
| 5001Z | | | | AA | 0-0 | 34-22-28 | D41393P | | 3 | | D41397P | 3 | | | ALL |
| 5002B | 24 | | G2 | AB | 11-0 | 34-22-38 | D41395P | | 2 | | D41397P | 18 | | | ALL |
| 5002R | 24 | | G2 | AB | 0-0 | 34-22-38 | D41395P | | 1 | | D41397P | 17 | | | ALL |
| 5002Z | | | | AB | 0-0 | 34-22-38 | D41395P | | 3 | | D41397P | 19 | | | ALL |
| 5003B | 24 | | G2 | AC | 23-0 | 34-22-39 | D41419P | | 5 | | D41395P | 5 | | | ALL |
| 5003R | 24 | | G2 | AC | 0-0 | 34-22-39 | D41419P | | 4 | | D41395P | 4 | | | ALL |
| 5003Z | | | | AC | 0-0 | 34-22-39 | D41419P | | 6 | | D41395P | 6 | | | ALL |
| 5004B | 24 | | G2 | AD | 11-0 | 34-22-18 | D41391P | | 5 | | D41397P | 5 | | | ALL |
| 5004R | 24 | | G2 | AD | 0-0 | 34-22-18 | D41391P | | 4 | | D41397P | 4 | | | ALL |
| 5004Z | | | | AD | 0-0 | 34-22-18 | D41391P | | 6 | | D41397P | 6 | | | ALL |
| 5005B | 24 | | G2 | AE | 10-0 | 31-31-41 | D41395P | | 8 | | D41495P | 3 | | | 001-099 |
| 5005B | 24 | | G2 | AE | 10-0 | 31-31-21 | D41395P | | 8 | | D41495P | 3 | | | 115-199 |
| 5005R | 24 | | G2 | AE | 0-0 | 31-31-41 | D41395P | | 9 | | D41495P | 2 | | | 001-099 |
| 5005R | 24 | | G2 | AE | 0-0 | 31-31-21 | D41395P | | 9 | | D41495P | 2 | | | 115-199 |
| 5005Z | | | | AE | 0-0 | 31-31-41 | D41395P | | 7 | | D41495P | 1 | | | 001-099 |
| 5005Z | | | | AE | 0-0 | 31-31-21 | D41395P | | 7 | | D41495P | 1 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 43

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | | |
|------------------------|-------------|----|----|---------------------------------------|-------------|---------|---------|------|------|---------|-------|------|------|--------------|-------------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4475 | 286N4475 | | | E/E RACK,INTERRACK CENTER (continued) | | | | | | | | | | | |
| 5006B | 24 | G2 | AF | 23-0 | 22-12-31 | D41395P | 13 | | | D41419P | 9 | | | ALL | |
| 5006R | 24 | G2 | AF | 0-0 | 22-12-31 | D41395P | 12 | | | D41419P | 8 | | | ALL | |
| 5006Z | | | AF | 0-0 | 22-12-31 | D41395P | 14 | | | D41419P | 10 | | | ALL | |
| 5007B | 24 | G2 | AG | 10-0 | SPARE | D41395P | 16 | | | D41391P | 8 | | | ALL | |
| 5007R | 24 | G2 | AG | 0-0 | SPARE | D41395P | 15 | | | D41391P | 7 | | | ALL | |
| 5007Z | | | AG | 0-0 | SPARE | D41395P | 17 | | | D41391P | 9 | | | ALL | |
| 5008B | 24 | G2 | AH | 12-0 | 22-12-31 | D41395P | 23 | | | D41393P | 8 | | | ALL | |
| 5008R | 24 | G2 | AH | 0-0 | 22-12-31 | D41395P | 22 | | | D41393P | 7 | | | ALL | |
| 5008Z | | | AH | 0-0 | 22-12-31 | D41395P | 24 | | | D41393P | 9 | | | ALL | |
| 5009B | 24 | G2 | AI | 11-0 | 22-12-31 | D41391P | 11 | | | D41393P | 5 | | | ALL | |
| 5009R | 24 | G2 | AI | 0-0 | 22-12-31 | D41391P | 10 | | | D41393P | 4 | | | ALL | |
| 5009Z | | | AI | 0-0 | 22-12-31 | D41391P | 12 | | | D41393P | 6 | | | ALL | |
| 5010B | 24 | G2 | AJ | 23-0 | SPARE | D41419P | 22 | | | D41395P | 25 | | | 001, 003-099 | |
| 5010B | 24 | G2 | AJ | 23-0 | SPARE | D41419P | 22 | | | D41395P | REF | JB | | 002 | |
| 5010B | 24 | G2 | AJ | 11-0 | SPARE | D41397P | 10 | | | D41395P | 25 | | | 115-199 | |
| 5010R | 24 | G2 | AJ | 0-0 | SPARE | D41419P | 21 | | | D41395P | 26 | | | 001, 003-099 | |
| 5010R | 24 | G2 | AJ | 0-0 | SPARE | D41419P | 21 | | | D41395P | REF | JB | | 002 | |
| 5010R | 24 | G2 | AJ | 0-0 | SPARE | D41397P | 11 | | | D41395P | 26 | | | 115-199 | |
| 5010Z | | | AJ | 0-0 | SPARE | D41419P | 23 | | | D41395P | 27 | | | 001, 003-099 | |
| 5010Z | | | AJ | 0-0 | SPARE | D41419P | 23 | | | D41395P | REF | JB | | 002 | |
| 5010Z | | | AJ | 0-0 | SPARE | D41397P | 12 | | | D41395P | 27 | | | 115-199 | |
| 5011B | 24 | G2 | AK | 12-0 | 22-15-11 | D41395P | 39 | | | D41393P | 20 | | | ALL | |
| 5011R | 24 | G2 | AK | 0-0 | 22-15-11 | D41395P | 38 | | | D41393P | 19 | | | ALL | |
| 5011Z | | | AK | 0-0 | 22-15-11 | D41395P | 40 | | | D41393P | 21 | | | ALL | |
| 5012B | 24 | G2 | AL | 10-0 | 22-15-11 | D41395P | 42 | | | D41391P | 20 | | | ALL | |
| 5012R | 24 | G2 | AL | 0-0 | 22-15-11 | D41395P | 41 | | | D41391P | 19 | | | ALL | |
| 5012Z | | | AL | 0-0 | 22-15-11 | D41395P | 43 | | | D41391P | 21 | | | ALL | |
| 5013B | 24 | G2 | AM | 22-0 | 22-22-11 | D41815P | 4 | | | D41399P | 4 | | | ALL | |
| 5013R | 24 | G2 | AM | 0-0 | 22-22-11 | D41815P | 3 | | | D41399P | 3 | | | ALL | |
| 5013Z | | | AM | 0-0 | 22-22-11 | D41815P | 5 | | | D41399P | 5 | | | ALL | |
| 5014B | 24 | G2 | AN | 24-0 | 22-41-11 | D41815P | 8 | | | D41401P | 1 | | | ALL | |
| 5014R | 24 | G2 | AN | 0-0 | 22-41-11 | D41815P | 7 | | | D41401P | 2 | | | ALL | |
| 5014Z | | | AN | 0-0 | 22-41-11 | D41815P | 9 | | | D41401P | 3 | | | ALL | |
| 5015B | 24 | G2 | AO | 23-0 | 22-21-11 | D41397P | 14 | | | D41399P | 9 | | | ALL | |
| 5015R | 24 | G2 | AO | 0-0 | 22-21-11 | D41397P | 13 | | | D41399P | 8 | | | ALL | |
| 5015Z | | | AO | 0-0 | 22-21-11 | D41397P | 15 | | | D41399P | 10 | | | ALL | |
| 5017B | 24 | G2 | AP | 25-0 | 31-51-34 | D41419P | 22 | | | D41599P | 6 | | | 115-199 | |
| 5017R | 24 | G2 | AP | 0-0 | 31-51-34 | D41419P | 21 | | | D41599P | 5 | | | 115-199 | |
| 5017Z | | | AP | 0-0 | 31-51-34 | D41419P | 23 | | | D41599P | 7 | | | 115-199 | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 44

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|---------------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4475 | 286N4475 | | | E/E RACK,INTERRACK CENTER (continued) | | | | | | | | | | | |
| 5019B | 22 | | GU | BD | 9-0 | 32-42-11 | D41397P | 21 | | | D41495P | 8 | | | 001-099 |
| 5019B | 24 | | G2 | BD | 9-0 | 32-42-11 | D41397P | 21 | | | D41495P | 8 | | | 115-199 |
| 5019R | 22 | | GU | BD | 0-0 | 32-42-11 | D41397P | 22 | | | D41495P | 9 | | | 001-099 |
| 5019R | 24 | | G2 | BD | 0-0 | 32-42-11 | D41397P | 22 | | | D41495P | 9 | | | 115-199 |
| 5019Z | | | | BD | 0-0 | 32-42-11 | D41397P | 23 | | | D41495P | 10 | | | ALL |
| 5020B | 24 | | G2 | BE | 11-0 | SPARE | D41391P | 26 | | | D41393P | 26 | | | ALL |
| 5020R | 24 | | G2 | BE | 0-0 | SPARE | D41391P | 25 | | | D41393P | 25 | | | ALL |
| 5020Z | | | | BE | 0-0 | SPARE | D41391P | 27 | | | D41393P | 27 | | | ALL |
| 5021B | 24 | | G2 | BF | 10-0 | SPARE | D41391P | 2 | | | D41395P | 54 | | | 115-199 |
| 5021R | 24 | | G2 | BF | 0-0 | SPARE | D41391P | 1 | | | D41395P | 53 | | | 115-199 |
| 5021Z | | | | BF | 0-0 | SPARE | D41391P | 3 | | | D41395P | 55 | | | 115-199 |
| 5022B | 22 | | GU | BG | 13-0 | 34-58-21 | D41393P | 38 | | | D41397P | 51 | | | 115-199 |
| 5022R | 22 | | GU | BG | 0-0 | 34-58-21 | D41393P | 39 | | | D41397P | 50 | | | 115-199 |
| 5022Z | | | | BG | 0-0 | 34-58-21 | D41393P | 18 | | | D41397P | 52 | | | 115-199 |
| 5023B | 24 | | G2 | BH | 11-0 | SPARE | D41397P | 28 | | | D41391P | 30 | | | 115-199 |
| 5023R | 24 | | G2 | BH | 0-0 | SPARE | D41397P | 27 | | | D41391P | 29 | | | 115-199 |
| 5023Z | | | | BH | 0-0 | SPARE | D41397P | 29 | | | D41391P | 31 | | | 115-199 |
| 5024B | 24 | | G2 | BI | 22-0 | SPARE | D41399P | 13 | | | D41815P | 33 | | | 001, 003-099 |
| 5024B | 24 | | G2 | BI | 22-0 | SPARE | D41399P | 13 | | | D41815P | REF | JB | | 002 |
| 5024B | 24 | | G2 | BI | 22-0 | SPARE | D41399P | 13 | | | D41815P | 34 | | | 115-199 |
| 5024R | 24 | | G2 | BI | 0-0 | SPARE | D41399P | 12 | | | D41815P | 18 | | | 001, 003-099 |
| 5024R | 24 | | G2 | BI | 0-0 | SPARE | D41399P | 12 | | | D41815P | REF | JB | | 002 |
| 5024R | 24 | | G2 | BI | 0-0 | SPARE | D41399P | 12 | | | D41815P | 33 | | | 115-199 |
| 5024Z | | | | BI | 0-0 | SPARE | D41399P | 14 | | | D41815P | 37 | | | 001, 003-099 |
| 5024Z | | | | BI | 0-0 | SPARE | D41399P | 14 | | | D41815P | REF | JB | | 002 |
| 5024Z | | | | BI | 0-0 | SPARE | D41399P | 14 | | | D41815P | 35 | | | 115-199 |
| 5025B | 24 | | G2 | BJ | 23-0 | SPARE | D41399P | 20 | | | D41397P | 25 | | | 001-099 |
| 5025B | 24 | | G2 | BJ | 23-0 | SPARE | D41399P | 20 | | | D41397P | 32 | | | 115-199 |
| 5025R | 24 | | G2 | BJ | 0-0 | SPARE | D41399P | 19 | | | D41397P | 24 | | | 001-099 |
| 5025R | 24 | | G2 | BJ | 0-0 | SPARE | D41399P | 19 | | | D41397P | 31 | | | 115-199 |
| 5025Z | | | | BJ | 0-0 | SPARE | D41399P | 21 | | | D41397P | 26 | | | 001-099 |
| 5025Z | | | | BJ | 0-0 | SPARE | D41399P | 21 | | | D41397P | 33 | | | 115-199 |
| 5027B | 24 | | G2 | KB | 25-0 | 31-31-42 | D41815P | 20 | | | D41403P | 2 | | | 001-099 |
| 5027B | 24 | | G2 | BL | 25-0 | 31-31-22 | D41815P | 20 | | | D41403P | 2 | | | 115-199 |
| 5027R | 24 | | G2 | KB | 0-0 | 31-31-42 | D41815P | 19 | | | D41403P | 1 | | | 001-099 |
| 5027R | 24 | | G2 | BL | 0-0 | 31-31-22 | D41815P | 19 | | | D41403P | 1 | | | 115-199 |
| 5027Z | | | | KB | 0-0 | 31-31-42 | D41815P | 21 | | | D41403P | 3 | | | 001-099 |
| 5027Z | | | | BL | 0-0 | 31-31-22 | D41815P | 21 | | | D41403P | 3 | | | 115-199 |
| 5028B | 24 | | G2 | KD | 25-0 | 31-31-42 | D41815P | 23 | | | D41403P | 5 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 45

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4475 | 286N4475 | | | | E/E RACK,INTERRACK CENTER (continued) | | | | | | | | | | |
| 5028B | 24 | | G2 | BM | 25-0 | 31-31-22 | D41815P | 24 | | | D41403P | 6 | | | 115-199 |
| 5028R | 24 | | G2 | KD | 0-0 | 31-31-42 | D41815P | 22 | | | D41403P | 4 | | | 001-099 |
| 5028R | 24 | | G2 | BM | 0-0 | 31-31-22 | D41815P | 23 | | | D41403P | 5 | | | 115-199 |
| 5028Z | | | | KD | 0-0 | 31-31-42 | D41815P | 24 | | | D41403P | 6 | | | 001-099 |
| 5028Z | | | | BM | 0-0 | 31-31-22 | D41815P | 22 | | | D41403P | 4 | | | 115-199 |
| 5029B | 24 | | G2 | KE | 25-0 | 31-31-43 | D41815P | 26 | | | D41403P | 8 | | | 001-099 |
| 5029B | 24 | | G2 | BN | 25-0 | 31-31-22 | D41815P | 27 | | | D41403P | 9 | | | 115-199 |
| 5029R | 24 | | G2 | KE | 0-0 | 31-31-43 | D41815P | 25 | | | D41403P | 7 | | | 001-099 |
| 5029R | 24 | | G2 | BN | 0-0 | 31-31-22 | D41815P | 26 | | | D41403P | 8 | | | 115-199 |
| 5029Z | | | | KE | 0-0 | 31-31-43 | D41815P | 27 | | | D41403P | 9 | | | 001-099 |
| 5029Z | | | | BN | 0-0 | 31-31-22 | D41815P | 25 | | | D41403P | 7 | | | 115-199 |
| 5030B | 24 | | G2 | KF | 28-0 | 31-31-43 | D41403P | 11 | | | D41419P | 17 | | | 001-099 |
| 5030B | 24 | | G2 | BO | 28-0 | 31-31-22 | D41403P | 11 | | | D41419P | 17 | | | 115-199 |
| 5030R | 24 | | G2 | KF | 0-0 | 31-31-43 | D41403P | 10 | | | D41419P | 16 | | | 001-099 |
| 5030R | 24 | | G2 | BO | 0-0 | 31-31-22 | D41403P | 10 | | | D41419P | 16 | | | 115-199 |
| 5030Z | | | | KF | 0-0 | 31-31-43 | D41403P | 12 | | | D41419P | 18 | | | 001-099 |
| 5030Z | | | | BO | 0-0 | 31-31-22 | D41403P | 12 | | | D41419P | 18 | | | 115-199 |
| 5031B | 24 | | G2 | BZ | 11-0 | 73-21-12 | D41393P | 34 | | | D41391P | 34 | | | 001-099 |
| 5031B | 24 | | G2 | BP | 11-0 | 73-21-12 | D41393P | 34 | | | D41391P | 34 | | | 115-199 |
| 5031R | 24 | | G2 | BZ | 0-0 | 73-21-12 | D41393P | 33 | | | D41391P | 33 | | | 001-099 |
| 5031R | 24 | | G2 | BP | 0-0 | 73-21-12 | D41393P | 33 | | | D41391P | 33 | | | 115-199 |
| 5031Z | | | | BZ | 0-0 | 73-21-12 | D41393P | 35 | | | D41391P | 35 | | | 001-099 |
| 5031Z | | | | BP | 0-0 | 73-21-12 | D41393P | 35 | | | D41391P | 35 | | | 115-199 |
| 5032B | 24 | | G2 | BR | 10-0 | 22-12-31 | D41815P | 28 | | | D41391P | 39 | | | 001-099 |
| 5032B | 24 | | G2 | AQ | 10-0 | 22-12-31 | D41815P | 28 | | | D41391P | 39 | | | 115-199 |
| 5032R | 24 | | G2 | BR | 0-0 | 22-12-31 | D41815P | 29 | | | D41391P | 37 | | | 001-099 |
| 5032R | 24 | | G2 | AQ | 0-0 | 22-12-31 | D41815P | 29 | | | D41391P | 37 | | | 115-199 |
| 5032Z | | | | BR | 0-0 | 22-12-31 | D41815P | 30 | | | D41391P | 38 | | | 001-099 |
| 5032Z | | | | AQ | 0-0 | 22-12-31 | D41815P | 30 | | | D41391P | 38 | | | 115-199 |
| 5038B | 22 | | GU | AW | 13-0 | 34-58-11 | D41815P | 54 | | | D41397P | 54 | | | 115-199 |
| 5038R | 22 | | GU | AW | 0-0 | 34-58-11 | D41815P | 53 | | | D41397P | 53 | | | 115-199 |
| 5038Z | | | | AW | 0-0 | 34-58-11 | D41815P | 55 | | | D41397P | 55 | | | 115-199 |
| 5041B | 24 | | G2 | KA | 10-0 | 34-45-01 | D41815P | 16 | | | D41391P | 49 | | | ALL |
| 5041R | 24 | | G2 | KA | 0-0 | 34-45-01 | D41815P | 15 | | | D41391P | 48 | | | ALL |
| 5041Z | | | | KA | 0-0 | 34-45-01 | D41815P | 17 | | | D41391P | 50 | | | ALL |
| 5042B | 24 | | G2 | BA | 10-0 | 34-45-01 | D41815P | 43 | | | D41391P | 2 | | | 003-099 |
| 5042R | 24 | | G2 | BA | 0-0 | 34-45-01 | D41815P | 42 | | | D41391P | 1 | | | 003-099 |
| 5042Z | | | | BA | 0-0 | 34-45-01 | D41815P | 44 | | | D41391P | 3 | | | 003-099 |
| 5043B | 22 | | GU | BB | 20-0 | 34-25-12 | D41395P | 26 | | | D41495P | 25 | | | 002 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 46

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | FT-IN | Diagram | From | | | To | | | Effectivity | |
|------------------------|-------------|----|----|---------------------------------------|----------|---------|-------|------|------|---------|-------|------|-------------|-----------------------|
| | GA | CO | TY | | | | Equip | Term | Type | Splice | Equip | Term | | Type |
| W4475 | 286N4475 | | | E/E RACK,INTERRACK CENTER (continued) | | | | | | | | | | |
| 5043R | 22 | GU | BB | 0-0 | 34-25-12 | D41395P | 25 | | | D41495P | 24 | | | 002 |
| 5043Z | | | BB | 0-0 | 34-25-12 | D41395P | 27 | | | D41495P | 26 | | | 002 |
| 5044B | 22 | GU | CD | 20-0 | 34-25-12 | D41395P | 54 | | | D41495P | 28 | | | 002 |
| 5044R | 22 | GU | CD | 0-0 | 34-25-12 | D41395P | 53 | | | D41495P | 27 | | | 002 |
| 5044Z | | | CD | 0-0 | 34-25-12 | D41395P | 55 | | | D41495P | 29 | | | 002 |
| 5052B | 22 | GU | CS | 14-0 | 34-58-21 | D41815P | 33 | | | D41393P | 18 | | | 002 |
| 5052R | 22 | GU | CS | 0-0 | 34-58-21 | D41815P | 18 | | | D41393P | 10 | | | 002 |
| 5052Z | | | CS | 0-0 | 34-58-21 | D41815P | 37 | | | D41393P | 28 | | | 002 |
| 5111B | 22 | X2 | FK | 18-0 | 34-22-38 | D41493P | 23 | | | D41815P | 46 | | | 115-199 |
| 5111R | 22 | X2 | FK | 0-0 | 34-22-38 | D41493P | 22 | | | D41815P | 45 | | | 115-199 |
| 5111Z | | | FK | 0-0 | 34-22-38 | D41493P | 24 | | | D41815P | 47 | | | 115-199 |
| 5114B | 24 | G2 | KC | 25-0 | 31-31-42 | D41815P | 35 | | | D41403P | 14 | | | 001-099 |
| 5114R | 24 | G2 | KC | 0-0 | 31-31-42 | D41815P | 34 | | | D41403P | 13 | | | 001-099 |
| 5114Z | | | KC | 0-0 | 31-31-42 | D41815P | 36 | | | D41403P | 15 | | | 001-099 |
| 5189B | 22 | GU | DY | 35-0 | 34-46-12 | D41395P | 47 | | | D41419P | 28 | | | 002 |
| 5189R | 22 | GU | DY | 0-0 | 34-46-12 | D41395P | 46 | | | D41419P | 27 | | | 002 |
| 5189Z | | | DY | 0-0 | 34-46-12 | D41395P | 48 | | | D41419P | 29 | | | 002 |
| W4477 | 286N4477 | | | E/E RACK,INTERRACK STANDBY/NEUTRAL | | | | | | | | | | |
| 0001 | 24 | GK | | 21-0 | SPARE | D41739P | 18 | | | D41451P | 1 | | | 001-099 |
| 0001 | 24 | GK | | 12-0 | SPARE | D41497P | 1 | | | D41451P | 1 | | | 115-199 |
| 0002 | 24 | GK | | 17-0 | 34-46-12 | D41497P | 2 | | | D41433P | 2 | | | ALL |
| 0004 | 24 | GK | | 10-0 | 34-46-12 | D41429P | 7 | | | D41433P | 7 | | | 001, 003-099, 115-199 |
| 0004 | 24 | GK | | 10-0 | SPARE | D41429P | 7 | | | D41433P | 7 | | | 002 |
| 0005 | 22 | GA | | 21-0 | 34-46-12 | D41451P | 17 | | | D41433P | 17 | | | ALL |
| 0006 | 22 | GA | | 9-0 | 33-16-51 | D41461P | 7 | | | D41463P | 17 | | | ALL |
| 0013 | 24 | GK | | 8-0 | SPARE | D41455J | 3 | | | D41453P | 19 | | | 001-099 |
| 0013 | 24 | GK | | 8-0 | 23-34-16 | D41455J | 3 | | | D41453P | 19 | | | 115-199 |
| 0014 | 24 | GK | | 22-0 | 23-31-13 | D41739P | 1 | | | D41453P | 20 | | | ALL |
| 0015 | 24 | GK | | 13-0 | 23-31-13 | D41497P | 5 | | | D41453P | 21 | | | ALL |
| 0016 | 22 | GA | | 25-0 | 31-31-01 | D41443P | 1 | | | D41739P | 2 | | | 001-099 |
| 0016 | 22 | GA | | 25-0 | 31-31-13 | D41443P | 1 | | | D41739P | 2 | | | 115-199 |
| 0017 | 22 | GA | | 25-0 | 31-31-61 | D41443P | 2 | | | D41739P | 3 | | | 001-099 |
| 0017 | 22 | GA | | 25-0 | 31-31-13 | D41443P | 2 | | | D41739P | 3 | | | 115-199 |
| 0018 | 22 | GA | | 25-0 | SPARE | D41443P | 3 | | | D41739P | 4 | | | 001-099 |
| 0019 | 22 | GA | | 25-0 | 31-31-01 | D41443P | 4 | | | D41739P | 5 | | | 001-099 |
| 0020 | 22 | GA | | 25-0 | 31-31-01 | D41443P | 5 | | | D41739P | 6 | | | 001-099 |
| 0020 | 22 | GA | | 25-0 | 31-31-13 | D41443P | 5 | | | D41739P | 6 | | | 115-199 |
| 0021 | 22 | GA | | 25-0 | 32-42-11 | D41445P | 26 | | | D41739P | 41 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 47

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | |
| 0021 | 22 | | GA | | 26-0 | 32-42-11 | | D41445P | | 26 | | D41739P | | 41 | | 115-199 |
| 0022 | 22 | | GA | | 22-0 | 31-31-01 | | D41443P | | 6 | | D41497P | | 6 | | 001-099 |
| 0022 | 22 | | GA | | 22-0 | 31-31-13 | | D41443P | | 6 | | D41497P | | 6 | | 115-199 |
| 0023 | 22 | | GA | | 22-0 | 31-31-01 | | D41443P | | 7 | | D41497P | | 7 | | 001-099 |
| 0023 | 22 | | GA | | 22-0 | 31-31-13 | | D41443P | | 7 | | D41497P | | 7 | | 115-199 |
| 0024 | 22 | | GA | | 26-0 | 31-31-01 | | D41443P | | 8 | | D41451P | | 5 | | 001-099 |
| 0024 | 22 | | GA | | 26-0 | 31-31-13 | | D41443P | | 8 | | D41451P | | 5 | | 115-199 |
| 0025 | 22 | | GA | | 25-0 | 31-31-61 | | D41739P | | 7 | | D41443P | | 9 | | 001-099 |
| 0025 | 22 | | GA | | 25-0 | 31-31-21 | | D41739P | | 7 | | D41443P | | 9 | | 115-199 |
| 0026 | 22 | | GA | | 25-0 | 31-31-61 | | D41739P | | 14 | | D41443P | | 16 | | 001-099 |
| 0026 | 22 | | GA | | 25-0 | 31-31-21 | | D41739P | | 14 | | D41443P | | 16 | | 115-199 |
| 0027 | 22 | | GA | | 26-0 | 31-31-61 | | D41451P | | 6 | | D41443P | | 17 | | 001-099 |
| 0027 | 22 | | GA | | 26-0 | 31-31-21 | | D41451P | | 6 | | D41443P | | 17 | | 115-199 |
| 0028 | 24 | | GK | | 27-0 | 31-31-61 | | D41443P | | 22 | | D41459P | | 2 | | 001-099 |
| 0028 | 24 | | GK | | 27-0 | 31-31-31 | | D41443P | | 22 | | D41459P | | 2 | | 115-199 |
| 0029 | 24 | | GK | | 27-0 | 31-31-61 | | D41443P | | 23 | | D41459P | | 3 | | 001-099 |
| 0029 | 24 | | GK | | 27-0 | 31-31-31 | | D41443P | | 23 | | D41459P | | 3 | | 115-199 |
| 0030 | 24 | | GK | | 27-0 | 31-31-61 | | D41443P | | 24 | | D41459P | | 4 | | 001-099 |
| 0030 | 24 | | GK | | 27-0 | 31-31-31 | | D41443P | | 24 | | D41459P | | 4 | | 115-199 |
| 0031 | 24 | | GK | | 26-0 | 34-53-11 | | D41451P | | 10 | | D41443P | | 26 | | 001-099 |
| 0031 | 24 | | GK | | 26-0 | SPARE | | D41451P | | 10 | | D41443P | | 26 | | 115-199 |
| 0032 | 24 | | GK | | 22-0 | 34-53-11 | | D41497P | | 8 | | D41443P | | 25 | | ALL |
| 0033 | 22 | | GA | | 22-0 | 32-42-11 | | D42185P | | 27 | | D41739P | | 42 | | ALL |
| 0034 | 22 | | GA | | 22-0 | 32-42-11 | | D42185P | | 28 | | D41739P | | 43 | | ALL |
| 0035 | 22 | | GA | | 22-0 | 32-61-11 | | D41497P | | 38 | | D41445P | | 27 | | 001-099 |
| 0035 | 22 | | GA | | 23-0 | 32-61-11 | | D41497P | | 38 | | D41445P | | 27 | | 115-199 |
| 0036 | 24 | | GK | | 26-0 | 27-32-11 | | D41463P | | 3 | | D41059P | | 3 | | ALL |
| 0037 | 24 | | GK | | 26-0 | 27-32-11 | | D41463P | | 4 | | D41059P | | 4 | | ALL |
| 0038 | 24 | | GK | | 26-0 | SPARE | | D41463P | | 5 | | D41059P | | 5 | | ALL |
| 0039 | 24 | | GK | | 26-0 | SPARE | | D41463P | | 6 | | D41059P | | 6 | | ALL |
| 0040 | 24 | | GK | | 26-0 | 27-32-11 | | D41463P | | 7 | | D41059P | | 7 | | ALL |
| 0041 | 24 | | GK | | 26-0 | 27-32-11 | | D41463P | | 8 | | D41059P | | 8 | | ALL |
| 0042 | 24 | | GK | | 24-0 | 31-51-11 | | D41451P | | 11 | | D41059P | | 26 | | ALL |
| 0043 | 24 | | GK | | 21-0 | 31-51-31 | | D41497P | | 9 | | D41059P | | 12 | | ALL |
| 0044 | 24 | | GK | | 22-0 | 32-61-11 | | D41497P | | 39 | | D41445P | | 28 | | 001-099 |
| 0044 | 24 | | GK | | 23-0 | 32-61-11 | | D41497P | | 39 | | D41445P | | 28 | | 115-199 |
| 0045 | 24 | | GK | | 26-0 | 31-51-33 | | D41453P | | 23 | | D41059P | | 14 | | 001-008, 010-099, 115-199 |
| 0045 | 24 | | GK | | 25-0 | 31-51-33 | | D41453P | | 23 | | D41059P | | 14 | | 009 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 48

Oct 09/2008



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | |
| 0077 | 24 | | GK | | 26-0 | 52-71-21 | D41445P | | 7 | | D41451P | | 43 | | 001-099 |
| 0077 | 24 | | GK | | 27-0 | 52-71-21 | D41445P | | 7 | | D41451P | | 43 | | 115-199 |
| 0078 | 22 | | GA | | 27-0 | 23-31-13 | D41445P | | 25 | | D41453P | | 50 | | 001-099 |
| 0078 | 22 | | GA | | 28-0 | 23-31-13 | D41445P | | 25 | | D41453P | | 50 | | 115-199 |
| 0079 | 22 | | GA | | 27-0 | 23-31-13 | D41445P | | 24 | | D41453P | | 51 | | 001-099 |
| 0079 | 22 | | GA | | 28-0 | 23-31-13 | D41445P | | 24 | | D41453P | | 51 | | 115-199 |
| 0080 | 22 | | GA | | 26-0 | 22-21-11 | D41451P | | 40 | | D41437P | | 2 | | ALL |
| 0081 | 24 | | GK | | 21-0 | SPARE | D41739P | | 17 | | D41459P | | 9 | | 115-199 |
| 0082 | 24 | | GK | | 21-0 | SPARE | D41739P | | 18 | | D41459P | | 10 | | 115-199 |
| 0083 | 22 | | GA | | 26-0 | 22-24-11 | D41451P | | 41 | | D41437P | | 3 | | ALL |
| 0084 | 22 | | GA | | 13-0 | 33-25-11 | D41497P | | 13 | | D41453P | | 38 | | 001-099 |
| 0084 | 22 | | GA | | 13-0 | SPARE | D41497P | | 13 | | D41453P | | 38 | | 115-199 |
| 0085 | 22 | | GA | | 22-0 | 33-25-21 | D41739P | | 19 | | D41453P | | 39 | | 001-099 |
| 0085 | 22 | | GA | | 22-0 | SPARE | D41739P | | 19 | | D41453P | | 39 | | 115-199 |
| 0086 | 22 | | GA | | 21-0 | 35-21-11 | D41451P | | 47 | | D41739P | | 20 | | ALL |
| 0087 | 22 | | GA | | 10-0 | 22-11-12 | D41429P | | 26 | | D41433P | | 27 | | ALL |
| 0088 | 22 | | GA | | 11-0 | 22-11-22 | D41431P | | 1 | | D41433P | | 28 | | 001-099 |
| 0088 | 22 | | GA | | 11-0 | 22-11-22 | D41431P | | 13 | | D41433P | | 28 | | 115-199 |
| 0089 | 20 | | GA | | 11-0 | SPARE | D41433P | | 32 | | D41431P | | 12 | | 001-099 |
| 0089 | 20 | | GA | | 12-0 | SPARE | D41739P | | 24 | | D41431P | | 14 | | 115-199 |
| 0090 | 22 | | GA | | 27-0 | SPARE | D41445P | | 8 | | D41451P | | 48 | | 115-199 |
| 0091 | 22 | | GA | | 27-0 | SPARE | D41445P | | 9 | | D41451P | | 49 | | 115-199 |
| 0092 | 22 | | GA | | 27-0 | 32-42-11 | D41445P | | 10 | | D41461P | | 32 | | 001-099 |
| 0092 | 22 | | GA | | 26-0 | SPARE | D41445P | | 10 | | D41739P | | 25 | | 115-199 |
| 0093 | 22 | | GA | | 27-0 | 32-42-11 | D41445P | | 11 | | D41461P | | 31 | | 001-099 |
| 0093 | 22 | | GA | | 26-0 | SPARE | D41445P | | 11 | | D41739P | | 26 | | 115-199 |
| 0094 | 22 | | GA | | 21-0 | SPARE | D41451P | | 34 | | D41433P | | 29 | | ALL |
| 0095 | 22 | | GA | | 17-0 | SPARE | D41497P | | 16 | | D41433P | | 30 | | 115-199 |
| 0096 | 22 | | GA | | 17-0 | SPARE | D41497P | | 17 | | D41433P | | 31 | | 115-199 |
| 0097 | 22 | | GA | | 25-0 | 34-12-62 | D42093P | | 8 | | D41431P | | 14 | | 001-099 |
| 0097 | 22 | | GA | | 25-0 | 34-12-62 | D42093P | | 8 | | D41431P | | 17 | | 115-199 |
| 0098 | 24 | | GK | | 28-0 | SPARE | D41443P | | 39 | | D41455J | | 8 | | 001-099 |
| 0099 | 20 | | GA | | 9-0 | 23-31-11 | D42185P | | 15 | | D41453P | | 43 | | ALL |
| 0100 | 22 | | GA | | 22-0 | 23-31-41 | D41453P | | 13 | | D41739P | | 29 | | ALL |
| 0101 | 22 | | GA | | 13-0 | 23-31-41 | D41453P | | 14 | | D41497P | | 18 | | ALL |
| 0102 | 22 | | GA | | 13-0 | 23-31-41 | D41453P | | 15 | | D41497P | | 19 | | ALL |
| 0103 | 22 | | GA | | 13-0 | 23-31-41 | D41453P | | 16 | | D41497P | | 20 | | ALL |
| 0104 | 22 | | GA | | 23-0 | 27-31-11 | D41451P | | 50 | | D41431P | | 2 | | 001-099 |
| 0104 | 22 | | GA | | 23-0 | 27-31-11 | D41451P | | 50 | | D41431P | | 19 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 50

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | |
| 0105 | 22 | | GA | | 21-0 | 27-23-11 | D41451P | | 2 | | D41433P | | 37 | | ALL |
| 0106 | 22 | | GA | | 21-0 | 27-23-11 | D41451P | | 3 | | D41433P | | 38 | | ALL |
| 0107 | 22 | | GA | | 13-0 | 23-31-41 | D41453P | | 12 | | D41497P | | 55 | | ALL |
| 0109 | 24 | | GK | | 26-0 | 27-32-11 | D41463P | | 11 | | D41059P | | 27 | | ALL |
| 0110 | 24 | | GK | | 19-0 | 31-51-41 | D41739P | | 32 | | D41059P | | 28 | | ALL |
| 0111 | 24 | | GK | | 19-0 | 31-51-42 | D41739P | | 33 | | D41059P | | 29 | | ALL |
| 0112 | 24 | | GK | | 26-0 | 23-21-11 | D41059P | | 30 | | D41453P | | 36 | | 001-008, 010-099, 115-199 |
| 0112 | 24 | | GK | | 25-0 | 23-21-11 | D41059P | | 30 | | D41453P | | 36 | | 009 |
| 0113 | 24 | | GK | | 19-0 | SPARE | D41433P | | 39 | | D41059P | | 9 | | 115-199 |
| 0114 | 24 | | GK | | 28-0 | 31-51-21 | D41445P | | 12 | | D41059P | | 31 | | 001-099 |
| 0114 | 24 | | GK | | 29-0 | 31-51-21 | D41445P | | 12 | | D41059P | | 31 | | 115-199 |
| 0115 | 24 | | GK | | 16-0 | 34-22-16 | D41429P | | 1 | | D41497P | | 4 | | 001-099 |
| 0115 | 24 | | GK | | 16-0 | 34-22-16 | D41429P | | 1 | | D41497P | | 45 | | 115-199 |
| 0116 | 24 | | GK | | 28-0 | 31-31-61 | D41455J | | 17 | | D41443P | | 33 | | 001-099 |
| 0116 | 24 | | GK | | 23-0 | SPARE | D41429P | | 2 | | D41443P | | 33 | | 115-199 |
| 0117 | 24 | | GK | | 24-0 | SPARE | D41431P | | 1 | | D41453P | | 52 | | 115-199 |
| 0118 | 24 | | GK | | 27-0 | 31-31-63 | D41443P | | 40 | | D41459P | | 26 | | 001-099 |
| 0118 | 22 | | GA | | 25-0 | 31-31-13 | D41443P | | 3 | | D41739P | | 4 | | 115-199 |
| 0119 | 22 | | GA | | 25-0 | 31-31-13 | D41443P | | 4 | | D41739P | | 5 | | 115-199 |
| 0120 | 24 | | GK | | 10-0 | 34-61-15 | D41433P | | 35 | | D41429P | | 3 | | 115-199 |
| 0121 | 24 | | GK | | 21-0 | SPARE | D41433P | | CAP | Y | D41451P | | 51 | | 115-199 |
| 0122 | 24 | | GK | | 22-0 | SPARE | D41433P | | CAP | Y | D41453P | | 53 | | 115-199 |
| 0123 | 24 | | GK | | 25-0 | 31-31-61 | D41443P | | 37 | | D41739P | | 31 | | 001-099 |
| 0123 | 24 | | GK | | 25-0 | SPARE | D41443P | | 37 | | D41739P | | 31 | | 115-199 |
| 0124 | 24 | | GK | | 26-0 | 31-31-01 | D41443P | | 54 | | D41451P | | 52 | | 001-099 |
| 0124 | 24 | | GK | | 26-0 | 31-31-13 | D41443P | | 54 | | D41451P | | 52 | | 115-199 |
| 0126 | 24 | | GK | | 21-0 | SPARE | D41429P | | 27 | | D41453P | | 46 | | 115-199 |
| 0127 | 24 | | GK | | 27-0 | SPARE | D41445P | | 14 | | D41451P | | 53 | | 115-199 |
| 0128 | 24 | | GK | | 23-0 | SPARE | D41451P | | 16 | | D41431P | | 3 | | ALL |
| 0129 | 24 | | GK | | 27-0 | 31-31-63 | D41443P | | 41 | | D41459P | | 27 | | 001-099 |
| 0129 | 24 | | GK | | 26-0 | SPARE | D41451P | | 35 | | D41443P | | 41 | | 115-199 |
| 0130 | 24 | | GK | | 24-0 | 31-51-43 | D41451P | | 36 | | D41059P | | 33 | | ALL |
| 0132 | 24 | | GK | | 26-0 | SPARE | D41451P | | 38 | | D41445P | | 13 | | 001-099 |
| 0132 | 24 | | GK | | 27-0 | SPARE | D41451P | | 38 | | D41445P | | 13 | | 115-199 |
| 0133 | 24 | | GK | | 13-0 | SPARE | D41453P | | 1 | | D41497P | | 26 | | ALL |
| 0134 | 24 | | GK | | 21-0 | SPARE | D41453P | | 2 | | D41429P | | 28 | | 115-199 |
| 0135 | 24 | | GK | | 22-0 | SPARE | D41453P | | 37 | | D41739P | | 34 | | ALL |
| 0136 | 24 | | GK | | 22-0 | SPARE | D41453P | | 40 | | D41433P | | 41 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 51

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|------------------------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | |
| 0138 | 24 | | GK | | 16-0 | SPARE | | D41459P | | CAP | Y | D41451P | 54 | | | 001-099 |
| 0139 | 24 | | GK | | 8-0 | SPARE | | D41459P | | | | D41461P | 3 | | | 115-199 |
| 0140 | 24 | | GK | | 8-0 | SPARE | | D41461P | | | | D41459P | 22 | | | ALL |
| 0141 | 24 | | GK | | 26-0 | SPARE | | D41463P | | | | D41059P | 34 | | | ALL |
| 0142 | 24 | | GK | | 17-0 | SPARE | | D41497P | | | | D41433P | 42 | | | 115-199 |
| 0143 | 24 | | GK | | 21-0 | SPARE | | D41497P | | | | D41059P | 35 | | | 115-199 |
| 0145 | 24 | | GK | | 19-0 | SPARE | | D41739P | | | | D41059P | 36 | | | 115-199 |
| 0146 | 24 | | GK | | 25-0 | 31-31-62 | | D41443P | | | | D41739P | 21 | | | 001-099 |
| 0146 | 24 | | GK | | 25-0 | SPARE | | D41739P | | | | D41443P | 43 | | | 115-199 |
| 0148 | 22 | | GA | | 26-0 | 27-21-12 | | D42185P | | | | D41437P | 4 | | | ALL |
| 0149 | 22 | | GA | | 26-0 | 27-31-12 | | D42185P | | | | D41437P | 5 | | | ALL |
| 0150 | 22 | | GA | | 26-0 | 27-61-12 | | D42185P | | | | D41437P | 6 | | | ALL |
| 0151 | 24 | | GK | | 19-0 | 31-51-41 | | D41433P | | | | D41059P | 32 | | | ALL |
| 0152 | 20 | | GA | | 12-0 | SPARE | | D41431P | | | | D41739P | 38 | | | 115-199 |
| 0153 | 22 | | GA | | 27-0 | 22-21-11 | | D41461P | | | | D41437P | 7 | | | ALL |
| 0154 | 22 | | GA | | 27-0 | 22-21-11 | | D41461P | | | | D41437P | 8 | | | ALL |
| 0155 | 22 | | GA | | 27-0 | 22-21-11 | | D41461P | | | | D41437P | 9 | | | ALL |
| 0156 | 22 | | GA | | 22-0 | SPARE | | D41453P | | | | D41739P | 15 | | | 001-099 |
| 0157 | 22 | | GA | | 26-0 | 27-41-11 | | D41437P | | | | D42185P | 5 | | | ALL |
| 0158 | 22 | | GA | | 26-0 | 27-41-11 | | D41437P | | | | D42185P | 6 | | | ALL |
| 0159 | 24 | | GK | | 25-0 | SPARE | | D41059P | | | | D42185P | 7 | | | ALL |
| 0160 | 24 | | GK | | 26-0 | 31-51-33 | | D41453P | | | | D41059P | 38 | | | 001-008, 010-099, 115-199 |
| 0160 | 24 | | GK | | 25-0 | 31-51-33 | | D41453P | | | | D41059P | 38 | | | 009 |
| 0161 | 24 | | GK | | 28-0 | 31-51-33 | | D41445P | | | | D41059P | 39 | | | 001-099 |
| 0161 | 24 | | GK | | 29-0 | 31-51-33 | | D41445P | | | | D41059P | 39 | | | 115-199 |
| 0162 | 24 | | GK | | 25-0 | 31-41-14 | | D41059P | | | | D42185P | 8 | | | ALL |
| 0163 | 24 | | GK | | 9-0 | 34-46-12 | | D41739P | | | | D41433P | 45 | | | ALL |
| 0164 | 24 | | GK | | 12-0 | 24-34-11 | | D41497P | | | | D42185P | 9 | | | ALL |
| 0165 | 24 | | GK | | 12-0 | SPARE | | D41497P | | | | D42185P | 10 | | | 115-199 |
| 0166 | 22 | | GA | | 22-0 | SPARE | | D41443P | | | | D41497P | 29 | | | 001-099 |
| 0166 | 22 | | GA | | 22-0 | 31-31-13 | | D41443P | | | | D41497P | 29 | | | 115-199 |
| 0167 | 24 | | GK | | 8-0 | 31-31-62 | | D41443P | | | | D41445P | 16 | | | 001-099 |
| 0167 | 24 | | GK | | 9-0 | 31-31-31 | | D41443P | | | | D41445P | 16 | | | 115-199 |
| 0168 | 24 | | GK | | 9-0 | 31-31-31 | | D41443P | | | | D41445P | 17 | | | 115-199 |
| 0169 | 24 | | GK | | 9-0 | 31-31-31 | | D41443P | | | | D41445P | 18 | | | 115-199 |
| 0170 | 22 | | GA | | 22-0 | 31-31-32 | | D41497P | | | | D41443P | 53 | | | 115-199 |
| 0171 | 22 | | GA | | 22-0 | SPARE | | D42185P | | | | D41739P | 37 | | | ALL |
| 0172 | 24 | | GK | | 27-0 | 52-71-21 | | D41445P | | | | D41451P | 55 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 52

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | | | |
| 0177 | 24 | | GK | | 13-0 | SPARE | D41497P | | 31 | | D41461P | | 21 | | 115-199 |
| 0178 | 24 | | GK | | 12-0 | 26-16-21 | D42185P | | 22 | | D41497P | | 32 | | ALL |
| 0179 | 24 | | GK | | 12-0 | 26-16-21 | D42185P | | 23 | | D41497P | | 33 | | ALL |
| 0180 | 24 | | GK | | 12-0 | 26-16-21 | D42185P | | 24 | | D41497P | | 34 | | ALL |
| 0181 | 22 | | GA | | 22-0 | SPARE | D41461P | | 22 | | D41433P | | 46 | | 115-199 |
| 0182 | 22 | | GA | | 22-0 | SPARE | D41461P | | 23 | | D41433P | | 47 | | 115-199 |
| 0183 | 24 | | GK | | 9-0 | 31-31-31 | D41445P | | 20 | | D41443P | | 34 | | 115-199 |
| 0184 | 24 | | GK | | 9-0 | 31-31-31 | D41445P | | 21 | | D41443P | | 35 | | 115-199 |
| 0185 | 24 | | GK | | 9-0 | 31-31-31 | D41445P | | 22 | | D41443P | | 36 | | 115-199 |
| 0188 | 24 | | GK | | 26-0 | SPARE | D41451P | | 33 | | D41437P | | 13 | | 001-099 |
| 0188 | 24 | | GK | | 24-0 | 34-46-12 | D41433P | | 51 | | D41437P | | 13 | | 115-199 |
| 0189 | 22 | | GA | | 8-0 | SPARE | D41455J | | 26 | | D41453P | | 54 | | 001-099 |
| 0191 | 22 | | GA | | 21-0 | 26-17-11 | D41451P | | 37 | | D41433P | | 21 | | ALL |
| 0192 | 22 | | GA | | 12-0 | 74-31-11 | D41497P | | 36 | | D41459P | | 12 | | 001-099 |
| 0192 | 22 | | GA | | 12-0 | SPARE | D41497P | | 36 | | D41459P | | 12 | | 115-199 |
| 0193 | 22 | | GA | | 9-0 | 74-31-11 | D41459P | | 35 | | D41463P | | 13 | | 001-099 |
| 0193 | 22 | | GA | | 14-0 | SPARE | D41497P | | 35 | | D41463P | | 13 | | 115-199 |
| 0194 | 24 | | GK | | 16-0 | 34-12-11 | D41497P | | 37 | | D41429P | | 2 | | 001-099 |
| 0194 | 24 | | GK | | 16-0 | 34-12-11 | D41497P | | 37 | | D41429P | | 32 | | 115-199 |
| 0195 | 24 | | GK | | 27-0 | 31-31-61 | D41443P | | 21 | | D41459P | | 1 | | 001-099 |
| 0195 | 24 | | GK | | 27-0 | 31-31-31 | D41443P | | 21 | | D41459P | | 1 | | 115-199 |
| 0196 | 20 | | GA | | 9-0 | SPARE | D41739P | | 40 | | D41433P | | 52 | | ALL |
| 0197 | 24 | | GK | | 25-0 | 31-31-32 | D41433P | | 32 | | D41443P | | 38 | | 115-199 |
| 0198 | 24 | | GK | | 25-0 | 31-31-32 | D41433P | | 33 | | D41443P | | 42 | | 115-199 |
| 0199 | 20 | | GA | | 21-0 | 34-46-12 | D41459P | | 13 | | D41433P | | 3 | | ALL |
| 0200 | 24 | | GK | | 8-0 | 23-51-11 | D41453P | | 7 | | D41455J | | 29 | | 001-099 |
| 0201 | 24 | | GK | | 23-0 | 23-12-31 | D41739P | | 45 | | D41455J | | 28 | | 001-099 |
| 0202 | 24 | | GK | | 26-0 | SPARE | D41445P | | 23 | | D41451P | | 48 | | 001-009 |
| 0202 | 24 | | GK | | 26-0 | SPARE | D41445P | | CAP | Y | D41451P | | 48 | | 010-099 |
| 0203 | 24 | | GK | | 26-0 | SPARE | D41445P | | 30 | | D41451P | | 49 | | 001-099 |
| 0204 | 24 | | GK | | 8-0 | SPARE | D41461P | | 8 | | D41459P | | 14 | | 001-099 |
| 0205 | 24 | | GK | | 8-0 | SPARE | D41461P | | 9 | | D41459P | | 15 | | 001-099 |
| 0206 | 24 | | GK | | 8-0 | SPARE | D41461P | | 10 | | D41459P | | 16 | | 001-099 |
| 0207 | 24 | | GK | | 8-0 | SPARE | D41461P | | 11 | | D41459P | | 17 | | 001-099 |
| 0208 | 24 | | GK | | 8-0 | SPARE | D41461P | | 15 | | D41459P | | 18 | | 001-099 |
| 0209 | 24 | | GK | | 8-0 | SPARE | D41461P | | 16 | | D41459P | | 19 | | 001-099 |
| 0210 | 22 | | GA | | 12-0 | SPARE | D41497P | | 3 | | D41459P | | 21 | | 001-099 |
| 0212 | 22 | | GA | | 26-0 | 27-09-14 | D42185P | | 25 | | D41437P | | 14 | | ALL |
| 0213 | 22 | | GA | | 26-0 | 27-09-14 | D42185P | | 26 | | D41437P | | 15 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 53

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | |
| 0214 | 22 | | GA | | 26-0 | 27-09-14 | D42185P | | | 29 | D41437P | | | 16 | ALL |
| 0215 | 22 | | GA | | 26-0 | 27-09-14 | D42185P | | | 30 | D41437P | | | 17 | ALL |
| 0216 | 22 | | GA | | 26-0 | 27-09-14 | D42185P | | | 31 | D41437P | | | 18 | ALL |
| 0217 | 22 | | GA | | 26-0 | 27-09-14 | D42185P | | | 10 | D41437P | | | 19 | 001-099 |
| 0217 | 22 | | GA | | 26-0 | 27-09-14 | D42185P | | | 32 | D41437P | | | 19 | 115-199 |
| 0218 | 24 | | GK | | 26-0 | SPARE | D41059P | | | 41 | D41463P | | | 14 | 001-099 |
| 0220 | 22 | | GA | | 26-0 | SPARE | D41437P | | | 10 | D42185P | | | 4 | 001-099 |
| 0222 | 24 | | GK | | 27-0 | SPARE | D41443P | | | 34 | D41459P | | | 9 | 001-099 |
| 0224 | 22 | | GA | | 26-0 | SPARE | D41453P | | | 28 | D41059P | | | 42 | 001-008, 010-099 |
| 0224 | 22 | | GA | | 25-0 | SPARE | D41453P | | | 28 | D41059P | | | 43 | 009 |
| 0228 | 24 | | GK | | 13-0 | SPARE | D41461P | | | 14 | D41497P | | | 35 | 001-099 |
| 0230 | 22 | | GA | | 23-0 | 23-34-15 | D41739P | | | 23 | D41455J | | | 23 | ALL |
| 0231 | 22 | | GA | | 8-0 | SPARE | D41455J | | | 25 | D41453P | | | 22 | 001-099 |
| 0232 | 24 | | GK | | 26-0 | 31-51-41 | D41463P | | | 44 | D41059P | | | 44 | ALL |
| 0233 | 24 | | GK | | 26-0 | 31-51-41 | D41463P | | | 45 | D41059P | | | 45 | ALL |
| 0238 | 22 | | GA | | 8-0 | 23-34-15 | D41453P | | | 27 | D41455J | | | 27 | ALL |
| 0243 | 22 | | GA | | 17-0 | 32-42-11 | D41451P | | | 32 | D41461P | | | 33 | 001-099 |
| 0245 | 24 | | GK | | 17-0 | 32-41-11 | D41461P | | | 55 | D41451P | | | 55 | 001-099 |
| 0246 | 22 | | GA | | 13-0 | 23-34-15 | D41497P | | | 46 | D41455J | | | 9 | 001-099 |
| 0246 | 22 | | GA | | 13-0 | 23-34-15 | D41455J | | | 9 | D41497P | | | 46 | 115-199 |
| 0247 | 22 | | GA | | 13-0 | 23-34-15 | D41497P | | | 47 | D41455J | | | 11 | 001-099 |
| 0247 | 22 | | GA | | 13-0 | 23-34-15 | D41455J | | | 11 | D41497P | | | 47 | 115-199 |
| 0248 | 22 | | GA | | 13-0 | 23-34-15 | D41497P | | | 48 | D41455J | | | 10 | 001-099 |
| 0248 | 22 | | GA | | 13-0 | 23-34-15 | D41455J | | | 10 | D41497P | | | 48 | 115-199 |
| 0249 | 22 | | GA | | 13-0 | 23-34-15 | D41497P | | | 49 | D41455J | | | 12 | 001-099 |
| 0249 | 22 | | GA | | 13-0 | 23-34-15 | D41455J | | | 12 | D41497P | | | 49 | 115-199 |
| 0250 | 22 | | GA | | 11-0 | 34-45-01 | D41739P | | | 36 | D41429P | | | 23 | ALL |
| 0251 | 24 | | GK | | 20-0 | 34-45-02 | D41429P | | | 24 | D41451P | | | 4 | ALL |
| 0252 | 22 | | GA | | 13-0 | 23-34-15 | D41455J | | | 13 | D41497P | | | 52 | 115-199 |
| 0259 | 22 | | GA | | 1-0 | 31-51-31 | D41059P | | | 51 | D41059P | | | 52 | 001-008, 115-199 |
| 0260 | 22 | | GA | | 1-0 | 31-51-31 | D41059P | | | 53 | D41059P | | | 54 | 001-008 |
| 0260 | 22 | | GA | | 2-0 | 31-51-31 | D41059P | | | 53 | D41059P | | | 54 | 115-199 |
| 0274 | 24 | | GK | | 19-0 | 31-51-34 | D41433P | | | 39 | D41059P | | | 42 | 009 |
| 0308 | 22 | | GA | | 13-0 | 23-31-19 | D41457P | | | 1 | D41497P | | | 28 | 001-099 |
| 0309 | 22 | | GA | | 13-0 | 23-31-19 | D41457P | | | 2 | D41497P | | | 40 | 001-099 |
| 0310 | 22 | | GA | | 13-0 | 23-31-19 | D41457P | | | 5 | D41497P | | | 43 | 001-099 |
| 0311 | 22 | | GA | | 13-0 | 23-31-19 | D41457P | | | 8 | D41497P | | | 23 | 001-099 |
| 0402 | 22 | | GA | | 25-0 | 31-31-42 | D41739P | | | 46 | D41443P | | | 38 | 001-099 |
| 0403 | 22 | | GA | | 25-0 | 31-31-42 | D41739P | | | 47 | D41443P | | | 55 | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 54

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|-------|---|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | |
| 0411 | 24 | | GK | | 12-0 | 34-22-29 | D41431P | | 15 | | D41429P | | 3 | | 001-099 |
| 0412 | 22 | | GA | | 23-0 | 23-34-15 | D41739P | | 49 | | D41455J | | 4 | | 001-099 |
| 0413 | 24 | | GK | | 10-0 | 34-22-39 | D41433P | | 26 | | D41429P | | 25 | | 001-099 |
| 0414 | 24 | | GK | | 12-0 | 34-22-19 | D41429P | | 28 | | D41739P | | 17 | | 001-099 |
| 0416 | 22 | | GA | | 17-0 | 22-14-11 | D41059P | | 46 | | D41429P | | 37 | | 001-008 |
| 0416 | 22 | | GA | | 18-0 | 22-14-11 | D41059P | | 46 | | D41429P | | 37 | | 009-099, 115-199 |
| 0452 | 22 | | GA | | 7-8 | 31-31-61 | D41445P | | 17 | | D43309P | | 5 | | 010-099 |
| 0453 | 22 | | GA | | 7-8 | 31-31-61 | D41445P | | 18 | | D43309P | | 6 | | 010-099 |
| 0454 | 22 | | GA | | 7-8 | 31-31-61 | D41445P | | 19 | | D43309P | | 7 | | 010-099 |
| 0455 | 22 | | GA | | 7-8 | 31-31-61 | D41445P | | 20 | | D43309P | | 8 | | 010-099 |
| 0456 | 22 | | GA | | 7-8 | 31-31-61 | D41445P | | 21 | | D43309P | | 1 | | 010-099 |
| 0457 | 22 | | GA | | 7-8 | 31-31-61 | D41445P | | 22 | | D43309P | | 2 | | 010-099 |
| 0458 | 22 | | GA | | 7-8 | 31-31-61 | D41445P | | 23 | | D43309P | | 3 | | 010-099 |
| 0459 | 22 | | GA | | 7-8 | 31-31-61 | D41445P | | 31 | | D43309P | | 4 | | 010-099 |
| 0501 | 22 | | CQ | | 32-0 | 34-46-12 | D41451P | | 53 | | D41433P | | 44 | | 002 |
| 2001B | 22 | | GB | BC | 13-0 | 23-31-21 | D41453P | | 30 | | D41497P | | 15 | | ALL |
| 2001R | 22 | | GB | BC | 0-0 | 23-31-21 | D41453P | | 29 | | D41497P | | 14 | | ALL |
| 2002B | 22 | | GB | BD | 22-0 | 23-31-21 | D41453P | | 32 | | D41739P | | 28 | | ALL |
| 2002R | 22 | | GB | BD | 0-0 | 23-31-21 | D41453P | | 31 | | D41739P | | 27 | | ALL |
| 2003B | 24 | | GL | BE | 26-0 | 27-32-11 | D41463P | | 2 | | D41059P | | 2 | | ALL |
| 2003R | 24 | | GL | BE | 0-0 | 27-32-11 | D41463P | | 1 | | D41059P | | 1 | | ALL |
| 2004B | 24 | | GL | AH | 27-0 | 31-31-51 | D41443P | | 32 | | D41459P | | 24 | | 001-099 |
| 2004B | 24 | | GL | BG | 27-0 | 31-31-31 | D41443P | | 52 | | D41459P | | 24 | | 115-199 |
| 2004R | 24 | | GL | AH | 0-0 | 31-31-51 | D41443P | | 31 | | D41459P | | 23 | | 001-099 |
| 2004R | 24 | | GL | BG | 0-0 | 31-31-31 | D41443P | | 51 | | D41459P | | 23 | | 115-199 |
| 2006B | 24 | | GL | BS | 8-0 | 23-51-11 | D41453P | | 5 | | D41455J | | 30 | | 001-099 |
| 2006R | 24 | | GL | BS | 0-0 | 23-51-11 | D41453P | | 6 | | D41455J | | 31 | | 001-099 |
| 2007B | 24 | | GL | BT | 8-0 | 23-51-11 | D41453P | | 9 | | D41455J | | 19 | | 001-099 |
| 2007R | 24 | | GL | BT | 0-0 | 23-51-11 | D41453P | | 8 | | D41455J | | 18 | | 001-099 |
| 2011B | 22 | | GB | AM | 8-0 | SPARE | D41455J | | 2 | | D41453P | | 18 | | 001-099 |
| 2011B | 22 | | GB | BR | 8-0 | 23-34-16 | D41453P | | 18 | | D41455J | | 2 | | 115-199 |
| 2011R | 22 | | GB | AM | 0-0 | SPARE | D41455J | | 1 | | D41453P | | 17 | | 001-099 |
| 2011R | 22 | | GB | BR | 0-0 | 23-34-16 | D41453P | | 17 | | D41455J | | 1 | | 115-199 |
| 2012B | 24 | | GL | AF | 8-0 | 23-21-11 | D41455J | | 6 | | D41453P | | 4 | | 001-099 |
| 2012R | 24 | | GL | AF | 0-0 | 23-21-11 | D41455J | | 5 | | D41453P | | 3 | | 001-099 |
| 2015B | 22 | | GB | AS | 13-0 | 23-31-19 | D41457P | | 4 | | D41497P | | 42 | | 001-099 |
| 2015R | 22 | | GB | AS | 0-0 | 23-31-19 | D41457P | | 3 | | D41497P | | 41 | | 001-099 |
| 2016B | 22 | | GB | AT | 13-0 | 23-31-19 | D41457P | | 6 | | D41497P | | 44 | | 001-099 |
| 2016R | 22 | | GB | AT | 0-0 | 23-31-19 | D41457P | | 7 | | D41497P | | 45 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 55

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4477 | 286N4477 | | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | | |
| 2017B | 22 | GB | AU | | 13-0 | 23-31-19 | D41457P | | 10 | | D41497P | | 31 | | 001-099 | | |
| 2017R | 22 | GB | AU | | 0-0 | 23-31-19 | D41457P | | 9 | | D41497P | | 30 | | 001-099 | | |
| 2502B | 24 | G2 | AN | | 22-0 | 23-51-13 | D41453P | | 33 | | D41433P | | 23 | | ALL | | |
| 2502R | 24 | G2 | AN | | 0-0 | 23-51-13 | D41453P | | 35 | | D41433P | | 22 | | ALL | | |
| 2502Z | | | AN | | 0-0 | 23-51-13 | D41453P | | 34 | | D41433P | | 24 | | ALL | | |
| 2509B | 22 | X2 | AV | | 20-0 | 34-22-38 | D41431P | | 9 | | D41497P | | 24 | | 115-199 | | |
| 2509R | 22 | X2 | AV | | 0-0 | 34-22-38 | D41431P | | 8 | | D41497P | | 21 | | 115-199 | | |
| 2509Z | | | AV | | 0-0 | 34-22-38 | D41431P | | 10 | | D41497P | | 25 | | 115-199 | | |
| 5001B | 24 | G2 | AA | | 10-0 | 34-46-12 | D41429P | | 5 | | D41433P | | 5 | | ALL | | |
| 5001R | 24 | G2 | AA | | 0-0 | 34-46-12 | D41429P | | 4 | | D41433P | | 4 | | ALL | | |
| 5001Z | | | AA | | 0-0 | 34-46-12 | D41429P | | 6 | | D41433P | | 6 | | ALL | | |
| 5002B | 24 | G2 | AB | | 10-0 | 34-46-12 | D41429P | | 10 | | D41433P | | 10 | | ALL | | |
| 5002R | 24 | G2 | AB | | 0-0 | 34-46-12 | D41429P | | 9 | | D41433P | | 9 | | ALL | | |
| 5002Z | | | AB | | 0-0 | 34-46-12 | D41429P | | 8 | | D41433P | | 8 | | ALL | | |
| 5003B | 24 | G2 | AC | | 10-0 | 34-46-12 | D41429P | | 13 | | D41433P | | 13 | | ALL | | |
| 5003R | 24 | G2 | AC | | 0-0 | 34-46-12 | D41429P | | 12 | | D41433P | | 12 | | ALL | | |
| 5003Z | | | AC | | 0-0 | 34-46-12 | D41429P | | 11 | | D41433P | | 11 | | ALL | | |
| 5004B | 24 | G2 | AD | | 10-0 | 34-46-12 | D41429P | | 16 | | D41433P | | 16 | | ALL | | |
| 5004R | 24 | G2 | AD | | 0-0 | 34-46-12 | D41429P | | 15 | | D41433P | | 15 | | ALL | | |
| 5004Z | | | AD | | 0-0 | 34-46-12 | D41429P | | 14 | | D41433P | | 14 | | ALL | | |
| 5005B | 24 | G2 | AE | | 21-0 | SPARE | D41451P | | 18 | | D41433P | | 18 | | ALL | | |
| 5005R | 24 | G2 | AE | | 0-0 | SPARE | D41451P | | 19 | | D41433P | | 19 | | ALL | | |
| 5005Z | | | AE | | 0-0 | SPARE | D41451P | | 20 | | D41433P | | 20 | | ALL | | |
| 5010B | 24 | G2 | AJ | | 25-0 | 31-31-41 | D41739P | | 8 | | D41443P | | 10 | | 001-099 | | |
| 5010B | 24 | G2 | AJ | | 25-0 | 31-31-21 | D41739P | | 8 | | D41443P | | 10 | | 115-199 | | |
| 5010R | 24 | G2 | AJ | | 0-0 | 31-31-41 | D41739P | | 9 | | D41443P | | 11 | | 001-099 | | |
| 5010R | 24 | G2 | AJ | | 0-0 | 31-31-21 | D41739P | | 9 | | D41443P | | 11 | | 115-199 | | |
| 5010Z | | | AJ | | 0-0 | 31-31-41 | D41739P | | 10 | | D41443P | | 12 | | 001-099 | | |
| 5010Z | | | AJ | | 0-0 | 31-31-21 | D41739P | | 10 | | D41443P | | 12 | | 115-199 | | |
| 5011B | 24 | G2 | AK | | 25-0 | 31-31-41 | D41739P | | 13 | | D41443P | | 15 | | 001-099 | | |
| 5011B | 24 | G2 | AK | | 25-0 | 31-31-21 | D41739P | | 13 | | D41443P | | 15 | | 115-199 | | |
| 5011R | 24 | G2 | AK | | 0-0 | 31-31-41 | D41739P | | 12 | | D41443P | | 14 | | 001-099 | | |
| 5011R | 24 | G2 | AK | | 0-0 | 31-31-21 | D41739P | | 12 | | D41443P | | 14 | | 115-199 | | |
| 5011Z | | | AK | | 0-0 | 31-31-41 | D41739P | | 11 | | D41443P | | 13 | | 001-099 | | |
| 5011Z | | | AK | | 0-0 | 31-31-21 | D41739P | | 11 | | D41443P | | 13 | | 115-199 | | |
| 5012B | 24 | G2 | AL | | 26-0 | 31-31-41 | D41451P | | 7 | | D41443P | | 18 | | 001-099 | | |
| 5012B | 24 | G2 | AL | | 26-0 | 31-31-21 | D41451P | | 7 | | D41443P | | 18 | | 115-199 | | |
| 5012R | 24 | G2 | AL | | 0-0 | 31-31-41 | D41451P | | 8 | | D41443P | | 19 | | 001-099 | | |
| 5012R | 24 | G2 | AL | | 0-0 | 31-31-21 | D41451P | | 8 | | D41443P | | 19 | | 115-199 | | |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 56

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | |
| 5012Z | | | | AL | 0-0 | 31-31-41 | D41451P | 9 | | | D41443P | 20 | | | 001-099 |
| 5012Z | | | | AL | 0-0 | 31-31-21 | D41451P | 9 | | | D41443P | 20 | | | 115-199 |
| 5014B | 24 | G2 | | AP | 28-0 | SPARE | D41443P | 28 | | | D41453P | 45 | | | 001-099 |
| 5014R | 24 | G2 | | AP | 0-0 | SPARE | D41443P | 27 | | | D41453P | 44 | | | 001-099 |
| 5014Z | | | | AP | 0-0 | SPARE | D41443P | 29 | | | D41453P | 41 | | | 001-099 |
| 5016B | 24 | G2 | | AR | 8-0 | SPARE | D41459P | 26 | | | D41461P | 13 | | | 115-199 |
| 5016R | 24 | G2 | | AR | 0-0 | SPARE | D41459P | 27 | | | D41461P | 12 | | | 115-199 |
| 5016Z | | | | AR | 0-0 | SPARE | D41459P | 28 | | | D41461P | 14 | | | 115-199 |
| 5017B | 24 | G2 | | CB | 25-0 | 31-31-42 | D41739P | 52 | | | D41443P | 52 | | | 001-099 |
| 5017R | 24 | G2 | | CB | 0-0 | 31-31-42 | D41739P | 51 | | | D41443P | 51 | | | 001-099 |
| 5017Z | | | | CB | 0-0 | 31-31-42 | D41739P | 53 | | | D41443P | 53 | | | 001-099 |
| 5018B | 24 | G2 | | AT | 8-0 | SPARE | D41459P | 32 | | | D41461P | 37 | | | 115-199 |
| 5018R | 24 | G2 | | AT | 0-0 | SPARE | D41459P | 33 | | | D41461P | 38 | | | 115-199 |
| 5018Z | | | | AT | 0-0 | SPARE | D41459P | 34 | | | D41461P | 39 | | | 115-199 |
| 5021B | 24 | G2 | | BF | 27-0 | 31-31-22 | D41443P | 46 | | | D42185P | 12 | | | 115-199 |
| 5021R | 24 | G2 | | BF | 0-0 | 31-31-22 | D41443P | 45 | | | D42185P | 11 | | | 115-199 |
| 5021Z | | | | BF | 0-0 | 31-31-22 | D41443P | 47 | | | D42185P | 13 | | | 115-199 |
| 5025B | 24 | G2 | | BX | 23-0 | 73-21-22 | D41431P | 5 | | | D42185P | 16 | | | 001-099 |
| 5025B | 24 | G2 | | BK | 23-0 | 73-21-22 | D41431P | 23 | | | D42185P | 16 | | | 115-199 |
| 5025R | 24 | G2 | | BX | 0-0 | 73-21-22 | D41431P | 6 | | | D42185P | 17 | | | 001-099 |
| 5025R | 24 | G2 | | BK | 0-0 | 73-21-22 | D41431P | 24 | | | D42185P | 17 | | | 115-199 |
| 5025Z | | | | BX | 0-0 | 73-21-22 | D41431P | 7 | | | D42185P | | | AA | 001-099 |
| 5025Z | | | | BK | 0-0 | 73-21-22 | D41431P | 25 | | | D42185P | | | AA | 115-199 |
| 5026B | 24 | G2 | | BY | 20-0 | 73-21-22 | D41429P | 29 | | | D42185P | 19 | | | 001-099 |
| 5026B | 24 | G2 | | BL | 20-0 | 73-21-22 | D41429P | 29 | | | D42185P | 19 | | | 115-199 |
| 5026R | 24 | G2 | | BY | 0-0 | 73-21-22 | D41429P | 30 | | | D42185P | 20 | | | 001-099 |
| 5026R | 24 | G2 | | BL | 0-0 | 73-21-22 | D41429P | 30 | | | D42185P | 20 | | | 115-199 |
| 5026Z | | | | BY | 0-0 | 73-21-22 | D41429P | 31 | | | D42185P | | | AA | 001-099 |
| 5026Z | | | | BL | 0-0 | 73-21-22 | D41429P | 31 | | | D42185P | | | AA | 115-199 |
| 5027B | 24 | G2 | | BZ | 11-0 | 34-46-12 | D41431P | 9 | | | D41433P | 49 | | | 009 |
| 5027B | 24 | G2 | | BO | 11-0 | 34-46-12 | D41433P | 49 | | | D41431P | 27 | | | 115-199 |
| 5027R | 24 | G2 | | BZ | 0-0 | 34-46-12 | D41431P | 8 | | | D41433P | 48 | | | 009 |
| 5027R | 24 | G2 | | BO | 0-0 | 34-46-12 | D41433P | 48 | | | D41431P | 26 | | | 115-199 |
| 5027Z | | | | BZ | 0-0 | 34-46-12 | D41431P | 10 | | | D41433P | 50 | | | 009 |
| 5027Z | | | | BO | 0-0 | 34-46-12 | D41433P | 50 | | | D41431P | 28 | | | 115-199 |
| 5028B | 24 | G2 | | BP | 26-0 | SPARE | D41463P | 15 | | | D41059P | 42 | | | 115-199 |
| 5028R | 24 | G2 | | BP | 0-0 | SPARE | D41463P | 14 | | | D41059P | 41 | | | 115-199 |
| 5028Z | | | | BP | 0-0 | SPARE | D41463P | 16 | | | D41059P | 43 | | | 115-199 |
| 5029B | 24 | G2 | | BQ | 10-0 | 34-46-12 | D41429P | 18 | | | D41433P | 54 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 57

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4477 | 286N4477 | | | E/E RACK,INTERRACK STANDBY/NEUTRAL (continued) | | | | | | | | | | | |
| 5029B | 24 | G2 | BQ | | 10-0 | 34-46-12 | D41429P | 54 | | | D41433P | 54 | | | 115-199 |
| 5029R | 24 | G2 | BQ | | 0-0 | 34-46-12 | D41429P | 17 | | | D41433P | 53 | | | 001-099 |
| 5029R | 24 | G2 | BQ | | 0-0 | 34-46-12 | D41429P | 53 | | | D41433P | 53 | | | 115-199 |
| 5029Z | | | BQ | | 0-0 | 34-46-12 | D41429P | 19 | | | D41433P | 55 | | | 001-099 |
| 5029Z | | | BQ | | 0-0 | 34-46-12 | D41429P | 55 | | | D41433P | 55 | | | 115-199 |
| 5054B | 24 | G2 | AW | | 18-0 | 34-45-02 | D41059P | CAP | Y | | D41429P | 51 | | | 001-008, 115-199 |
| 5054B | 24 | G2 | AW | | 18-0 | 34-45-02 | D41059P | 53 | | | D41429P | 51 | | | 009-099 |
| 5054R | 24 | G2 | AW | | 0-0 | 34-45-02 | D41059P | CAP | Y | | D41429P | 50 | | | 001-008, 115-199 |
| 5054R | 24 | G2 | AW | | 0-0 | 34-45-02 | D41059P | 52 | | | D41429P | 50 | | | 009-099 |
| 5054Z | | | AW | | 0-0 | 34-45-02 | D41059P | DED | | | D41429P | 52 | | | ALL |
| 5060B | 22 | GU | BF | | 30-0 | 34-25-13 | D41739P | 25 | | | D42185P | 12 | | | 002 |
| 5060R | 22 | GU | BF | | 0-0 | 34-25-13 | D41739P | 24 | | | D42185P | 11 | | | 002 |
| 5060Z | | | BF | | 0-0 | 34-25-13 | D41739P | 26 | | | D42185P | 13 | | | 002 |
| 5061B | 24 | G2 | BB | | 26-0 | 31-51-34 | D41463P | 22 | | | D41059P | 48 | | | 009 |
| 5061R | 24 | G2 | BB | | 0-0 | 31-51-34 | D41463P | 21 | | | D41059P | 47 | | | 009 |
| 5061Z | | | BB | | 0-0 | 31-51-34 | D41463P | 23 | | | D41059P | 49 | | | 009 |
| 5086B | 22 | GU | AZ | | 35-0 | 34-43-14 | D00111 | 2 | | | SP00487 | | 9 | | 002 |
| 5086R | 22 | GU | AZ | | 0-0 | 34-43-14 | D00111 | 1 | | | SP00485 | | 9 | | 002 |
| 5086Z | | | AZ | | 0-0 | 34-43-14 | D00111 | DED | | | SP00489 | | 9 | | 002 |
| 5126B | 22 | GU | AI | | 12-0 | 34-46-12 | D41431P | 9 | | | D41433P | 34 | | | 002 |
| 5126R | 22 | GU | AI | | 0-0 | 34-46-12 | D41431P | 8 | | | D41433P | 33 | | | 002 |
| 5126Z | | | AI | | 0-0 | 34-46-12 | D41431P | 10 | | | D41433P | 35 | | | 002 |
| 5127B | 22 | GU | FA | | 12-0 | 34-46-12 | D41429P | 40 | | | D41433P | 47 | | | 002 |
| 5127R | 22 | GU | FA | | 0-0 | 34-46-12 | D41429P | 39 | | | D41433P | 46 | | | 002 |
| 5127Z | | | FA | | 0-0 | 34-46-12 | D41429P | 38 | | | D41433P | 48 | | | 002 |
| FRAA | | | | | 0-0 | 73-21-22 | D42185P | | | AA | D42185P | 21 | | | ALL |
| W4479 | 286N4479 | | | E/E RACKS- | | | | | | | | | | | |
| 0001 | 24 | GK | | | 8-0 | 34-61-11 | D41565P | 7 | | | D41817P | 19 | | | 001-099 |
| 0001 | 24 | GK | | | 10-0 | 34-61-11 | D41565P | 7 | | | D41817P | 19 | | | 115-199 |
| 0002 | 24 | GK | | | 8-0 | 34-61-23 | D41563P | 21 | | | D41565P | 21 | | | 001-099 |
| 0002 | 24 | GK | | | 9-0 | 34-61-23 | D41563P | 21 | | | D41565P | 21 | | | 115-199 |
| 0003 | 24 | GK | | | 8-0 | 34-61-23 | D41563P | 22 | | | D41565P | 22 | | | 001-099 |
| 0003 | 24 | GK | | | 9-0 | 34-61-23 | D41563P | 22 | | | D41565P | 22 | | | 115-199 |
| 0004 | 24 | GK | | | 8-0 | 34-61-23 | D41563P | 26 | | | D41565P | 26 | | | 001-099 |
| 0004 | 24 | GK | | | 9-0 | 34-61-23 | D41563P | 26 | | | D41565P | 26 | | | 115-199 |
| 0005 | 24 | GK | | | 8-0 | 34-61-23 | D41563P | 27 | | | D41565P | 27 | | | 001-099 |
| 0005 | 24 | GK | | | 9-0 | 34-61-23 | D41563P | 27 | | | D41565P | 27 | | | 115-199 |
| 0006 | 24 | GK | | | 8-0 | 34-61-23 | D41563P | 28 | | | D41565P | 28 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 58

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4479 | 286N4479 | | | E/E RACKS- (continued) | | | | | | | | | | | |
| 0006 | 24 | | GK | | 9-0 | 34-61-23 | D41563P | | 28 | | D41565P | | 28 | | 115-199 |
| 0007 | 24 | | GK | | 8-0 | 34-61-23 | D41563P | | 29 | | D41565P | | 29 | | 001-099 |
| 0007 | 24 | | GK | | 9-0 | 34-61-23 | D41563P | | 29 | | D41565P | | 29 | | 115-199 |
| 0008 | 24 | | GK | | 8-0 | 34-61-23 | D41563P | | 30 | | D41565P | | 30 | | 001-099 |
| 0008 | 24 | | GK | | 9-0 | 34-61-23 | D41563P | | 30 | | D41565P | | 30 | | 115-199 |
| 0009 | 24 | | GK | | 8-0 | 34-61-23 | D41563P | | 31 | | D41565P | | 31 | | 001-099 |
| 0009 | 24 | | GK | | 9-0 | 34-61-23 | D41563P | | 31 | | D41565P | | 31 | | 115-199 |
| 0010 | 24 | | GK | | 8-0 | 34-61-23 | D41563P | | 32 | | D41565P | | 32 | | 001-099 |
| 0010 | 24 | | GK | | 9-0 | 34-61-23 | D41563P | | 32 | | D41565P | | 32 | | 115-199 |
| 0011 | 24 | | GK | | 8-0 | 34-61-23 | D41563P | | 33 | | D41565P | | 33 | | 001-099 |
| 0011 | 24 | | GK | | 9-0 | 34-61-23 | D41563P | | 33 | | D41565P | | 33 | | 115-199 |
| 0013 | 24 | | GK | | 8-0 | 34-22-35 | D41595P | | 25 | | D41567P | | 34 | | 001-099 |
| 0013 | 24 | | GK | | 9-0 | 34-22-35 | D41595P | | 25 | | D41567P | | 34 | | 115-199 |
| 0014 | 24 | | GK | | 8-0 | 34-22-35 | D41595P | | 26 | | D41567P | | 35 | | 001-099 |
| 0014 | 24 | | GK | | 9-0 | 34-22-35 | D41595P | | 26 | | D41567P | | 35 | | 115-199 |
| 0015 | 24 | | GK | | 8-0 | 34-22-35 | D41595P | | 27 | | D41567P | | 36 | | 001-099 |
| 0015 | 24 | | GK | | 9-0 | 34-22-35 | D41595P | | 27 | | D41567P | | 36 | | 115-199 |
| 0016 | 24 | | GK | | 8-0 | 34-22-35 | D41595P | | 22 | | D41567P | | 31 | | 001-099 |
| 0016 | 24 | | GK | | 9-0 | 34-22-35 | D41595P | | 22 | | D41567P | | 31 | | 115-199 |
| 0017 | 24 | | GK | | 8-0 | 34-22-35 | D41595P | | 23 | | D41567P | | 32 | | 001-099 |
| 0017 | 24 | | GK | | 9-0 | 34-22-35 | D41595P | | 23 | | D41567P | | 32 | | 115-199 |
| 0018 | 24 | | GK | | 8-0 | 34-22-35 | D41595P | | 24 | | D41567P | | 33 | | 001-099 |
| 0018 | 24 | | GK | | 9-0 | 34-22-35 | D41595P | | 24 | | D41567P | | 33 | | 115-199 |
| 0019 | 22 | | GA | | 8-0 | 34-61-11 | D41565P | | 41 | | D41563P | | 10 | | 001-099 |
| 0019 | 22 | | GA | | 9-0 | SPARE | D41565P | | 41 | | D41563P | | 10 | | 115-199 |
| 0020 | 22 | | GA | | 10-0 | SPARE | D41567P | | 37 | | D41563P | | 11 | | 001-099 |
| 0020 | 22 | | GA | | 11-0 | SPARE | D41567P | | 37 | | D41563P | | 11 | | 115-199 |
| 0021 | 22 | | GA | | 8-0 | SPARE | D41567P | | 38 | | D41595P | | 28 | | 001-099 |
| 0021 | 22 | | GA | | 9-0 | SPARE | D41567P | | 38 | | D41595P | | 28 | | 115-199 |
| 0022 | 22 | | GA | | 7-0 | SPARE | D41595P | | 38 | | D41743P | | 4 | | 001-099 |
| 0022 | 22 | | GA | | 8-0 | SPARE | D41595P | | 38 | | D41743P | | 4 | | 115-199 |
| 0023 | 22 | | GA | | 7-0 | 22-14-11 | D41595P | | 39 | | D41743P | | 5 | | 001-099 |
| 0023 | 22 | | GA | | 8-0 | 22-14-11 | D41595P | | 39 | | D41743P | | 5 | | 115-199 |
| 0024 | 22 | | GA | | 7-0 | 22-14-11 | D41595P | | 40 | | D41743P | | 6 | | 001-099 |
| 0024 | 22 | | GA | | 8-0 | 22-14-11 | D41595P | | 40 | | D41743P | | 6 | | 115-199 |
| 0025 | 22 | | GA | | 7-0 | 22-14-11 | D41595P | | 41 | | D41743P | | 7 | | 001-099 |
| 0025 | 22 | | GA | | 8-0 | 22-14-11 | D41595P | | 41 | | D41743P | | 7 | | 115-199 |
| 0026 | 22 | | GA | | 7-0 | 22-14-11 | D41595P | | 42 | | D41743P | | 8 | | 001-099 |
| 0026 | 22 | | GA | | 8-0 | 22-14-11 | D41595P | | 42 | | D41743P | | 8 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 59

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4479 | 286N4479 | | | E/E RACKS- (continued) | | | | | | | | | | | |
| 0028 | 22 | | GA | | 8-0 | 22-14-11 | D41567P | 46 | | | D41595P | 44 | | | 001-099 |
| 0028 | 22 | | GA | | 11-0 | 22-14-11 | D41567P | 46 | | | D41595P | 44 | | | 115-199 |
| 0029 | 22 | | GA | | 8-0 | 22-15-12 | D41567P | 47 | | | D41595P | 48 | | | 001-099 |
| 0029 | 22 | | GA | | 11-0 | 22-15-12 | D41567P | 47 | | | D41595P | 48 | | | 115-199 |
| 0030 | 22 | | GA | | 6-0 | 22-15-12 | D41565P | 48 | | | D41595P | 49 | | | 001-099 |
| 0030 | 22 | | GA | | 7-0 | 22-15-12 | D41565P | 48 | | | D41595P | 49 | | | 115-199 |
| 0034 | 24 | | GK | | 10-0 | 34-22-17 | D41563P | 55 | | | D41569P | 28 | | | 001-099 |
| 0034 | 24 | | GK | | 11-0 | 34-22-17 | D41563P | 55 | | | D41569P | 34 | | | 115-199 |
| 0035 | 24 | | GK | | 9-0 | SPARE | D41817P | 30 | | | D41743P | 18 | | | 001, 003-099 |
| 0035 | 24 | | GK | | 9-0 | SPARE | D41817P | REF | JB | | D41743P | 18 | | | 002 |
| 0036 | 24 | | GK | | 10-0 | SPARE | D41817P | 29 | | | D41819P | 14 | | | 001, 003-099 |
| 0036 | 24 | | GK | | 10-0 | 34-46-14 | D41817P | 29 | | | D41819P | 14 | | | 002 |
| 0041 | 24 | | GK | | 9-0 | 34-61-23 | D41817P | 9 | | | D41743P | 10 | | | 001-099 |
| 0041 | 24 | | GK | | 11-0 | 34-61-23 | D41817P | 9 | | | D41743P | 10 | | | 115-199 |
| 0043 | 24 | | GK | | 9-0 | 34-61-23 | D41817P | 11 | | | D41743P | 12 | | | 001-099 |
| 0043 | 24 | | GK | | 11-0 | 34-61-23 | D41817P | 11 | | | D41743P | 12 | | | 115-199 |
| 0044 | 24 | | GK | | 9-0 | 34-61-23 | D41817P | 12 | | | D41743P | 13 | | | 001-099 |
| 0044 | 24 | | GK | | 11-0 | 34-61-23 | D41817P | 12 | | | D41743P | 13 | | | 115-199 |
| 0045 | 24 | | GK | | 9-0 | 34-61-23 | D41817P | 10 | | | D41743P | 11 | | | 001-099 |
| 0045 | 24 | | GK | | 11-0 | 34-61-23 | D41817P | 10 | | | D41743P | 11 | | | 115-199 |
| 0046 | 22 | | GA | | 10-0 | 22-32-15 | D41563P | 50 | | | D41567P | 50 | | | 001-099 |
| 0046 | 22 | | GA | | 11-0 | 22-32-15 | D41563P | 50 | | | D41567P | 50 | | | 115-199 |
| 0047 | 22 | | GA | | 7-0 | 22-14-11 | D41743P | 14 | | | D41595P | 50 | | | 001-099 |
| 0047 | 22 | | GA | | 8-0 | 22-14-11 | D41743P | 14 | | | D41595P | 50 | | | 115-199 |
| 0048 | 22 | | GA | | 10-0 | SPARE | D41567P | 51 | | | D41743P | 15 | | | 115-199 |
| 0054 | 24 | | GK | | 10-0 | 34-22-37 | D41567P | 54 | | | D41569P | 29 | | | 001-099 |
| 0054 | 24 | | GK | | 10-0 | 34-22-37 | D41567P | 54 | | | D41569P | 54 | | | 115-199 |
| 0501 | 22 | | CQ | | 14-0 | 34-46-14 | D41817P | 30 | | | D41819P | 24 | | | 002 |
| 5001B | 24 | | G2 | AA | 8-0 | 34-61-11 | D41565P | 2 | | | D41817P | 14 | | | 001-099 |
| 5001B | 24 | | G2 | AA | 10-0 | 34-61-11 | D41565P | 2 | | | D41817P | 14 | | | 115-199 |
| 5001R | 24 | | G2 | AA | 0-0 | 34-61-11 | D41565P | 3 | | | D41817P | 15 | | | ALL |
| 5001Z | | | | AA | 0-0 | 34-61-11 | D41565P | 1 | | | D41817P | 13 | | | ALL |
| 5002B | 24 | | G2 | AB | 8-0 | 34-61-11 | D41565P | 5 | | | D41817P | 17 | | | 001-099 |
| 5002B | 24 | | G2 | AB | 10-0 | 34-61-11 | D41565P | 5 | | | D41817P | 17 | | | 115-199 |
| 5002R | 24 | | G2 | AB | 0-0 | 34-61-11 | D41565P | 6 | | | D41817P | 18 | | | ALL |
| 5002Z | | | | AB | 0-0 | 34-61-11 | D41565P | 4 | | | D41817P | 16 | | | ALL |
| 5003B | 24 | | G2 | AC | 8-0 | 34-61-11 | D41565P | 10 | | | D41817P | 22 | | | 001-099 |
| 5003B | 24 | | G2 | AC | 10-0 | 34-61-11 | D41565P | 10 | | | D41817P | 22 | | | 115-199 |
| 5003R | 24 | | G2 | AC | 0-0 | 34-61-11 | D41565P | 9 | | | D41817P | 21 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 60

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4479 | 286N4479 | | | E/E RACKS- (continued) | | | | | | | | | | | |
| 5003Z | | | | AC | 0-0 | 34-61-11 | D41565P | 8 | | | D41817P | 20 | | | ALL |
| 5004B | 24 | G2 | | AD | 10-0 | 34-61-12 | D41567P | 2 | | | D41563P | 2 | | | 001-099 |
| 5004B | 24 | G2 | | AD | 11-0 | 34-61-12 | D41567P | 2 | | | D41563P | 2 | | | 115-199 |
| 5004R | 24 | G2 | | AD | 0-0 | 34-61-12 | D41567P | 1 | | | D41563P | 1 | | | ALL |
| 5004Z | | | | AD | 0-0 | 34-61-12 | D41567P | 3 | | | D41563P | 3 | | | ALL |
| 5005B | 24 | G2 | | AE | 10-0 | 34-61-12 | D41569P | 5 | | | D41563P | 5 | | | 001-099 |
| 5005B | 24 | G2 | | AE | 12-0 | 34-61-12 | D41569P | 5 | | | D41563P | 5 | | | 115-199 |
| 5005R | 24 | G2 | | AE | 0-0 | 34-61-12 | D41569P | 4 | | | D41563P | 4 | | | ALL |
| 5005Z | | | | AE | 0-0 | 34-61-12 | D41569P | 6 | | | D41563P | 6 | | | ALL |
| 5006B | 24 | G2 | | AF | 10-0 | 34-61-15 | D41569P | 8 | | | D41563P | 8 | | | 001-099 |
| 5006B | 24 | G2 | | AF | 12-0 | 34-61-15 | D41569P | 8 | | | D41563P | 8 | | | 115-199 |
| 5006R | 24 | G2 | | AF | 0-0 | 34-61-15 | D41569P | 7 | | | D41563P | 7 | | | ALL |
| 5006Z | | | | AF | 0-0 | 34-61-15 | D41569P | 9 | | | D41563P | 9 | | | ALL |
| 5007B | 24 | G2 | | AG | 8-0 | 34-61-23 | D41563P | 24 | | | D41565P | 24 | | | 001-099 |
| 5007B | 24 | G2 | | AG | 10-0 | 34-61-23 | D41563P | 24 | | | D41565P | 24 | | | 115-199 |
| 5007R | 24 | G2 | | AG | 0-0 | 34-61-23 | D41563P | 23 | | | D41565P | 23 | | | ALL |
| 5007Z | | | | AG | 0-0 | 34-61-23 | D41563P | 25 | | | D41565P | 25 | | | ALL |
| 5008B | 24 | G2 | | AH | 8-0 | 34-61-23 | D41563P | 13 | | | D41565P | 13 | | | 001-099 |
| 5008B | 24 | G2 | | AH | 9-0 | 34-61-23 | D41563P | 13 | | | D41565P | 13 | | | 115-199 |
| 5008R | 24 | G2 | | AH | 0-0 | 34-61-23 | D41563P | 12 | | | D41565P | 12 | | | ALL |
| 5008Z | | | | AH | 0-0 | 34-61-23 | D41563P | 14 | | | D41565P | 14 | | | ALL |
| 5009B | 24 | G2 | | AI | 8-0 | 34-61-23 | D41563P | 16 | | | D41565P | 16 | | | 001-099 |
| 5009B | 24 | G2 | | AI | 9-0 | 34-61-23 | D41563P | 16 | | | D41565P | 16 | | | 115-199 |
| 5009R | 24 | G2 | | AI | 0-0 | 34-61-23 | D41563P | 15 | | | D41565P | 15 | | | ALL |
| 5009Z | | | | AI | 0-0 | 34-61-23 | D41563P | 17 | | | D41565P | 17 | | | ALL |
| 5010B | 24 | G2 | | AJ | 8-0 | 34-61-23 | D41563P | 19 | | | D41565P | 19 | | | 001-099 |
| 5010B | 24 | G2 | | AJ | 9-0 | 34-61-23 | D41563P | 19 | | | D41565P | 19 | | | 115-199 |
| 5010R | 24 | G2 | | AJ | 0-0 | 34-61-23 | D41563P | 18 | | | D41565P | 18 | | | ALL |
| 5010Z | | | | AJ | 0-0 | 34-61-23 | D41563P | 20 | | | D41565P | 20 | | | ALL |
| 5011B | 24 | G2 | | AK | 10-0 | 34-22-18 | D41563P | 36 | | | D41569P | 2 | | | 001-099 |
| 5011B | 24 | G2 | | AK | 12-0 | 34-22-18 | D41563P | 36 | | | D41569P | 2 | | | 115-199 |
| 5011R | 24 | G2 | | AK | 0-0 | 34-22-18 | D41563P | 35 | | | D41569P | 1 | | | ALL |
| 5011Z | | | | AK | 0-0 | 34-22-18 | D41563P | 37 | | | D41569P | 3 | | | ALL |
| 5012B | 24 | G2 | | AL | 10-0 | 34-22-19 | D41563P | 39 | | | D41567P | 5 | | | 001-099 |
| 5012B | 24 | G2 | | AL | 11-0 | 34-22-19 | D41563P | 39 | | | D41567P | 5 | | | 115-199 |
| 5012R | 24 | G2 | | AL | 0-0 | 34-22-19 | D41563P | 38 | | | D41567P | 4 | | | ALL |
| 5012Z | | | | AL | 0-0 | 34-22-19 | D41563P | 40 | | | D41567P | 6 | | | ALL |
| 5013B | 24 | G2 | | AM | 8-0 | 34-22-28 | D41565P | 36 | | | D41563P | 42 | | | 001-099 |
| 5013B | 24 | G2 | | AM | 9-0 | SPARE | D41565P | 36 | | | D41563P | 42 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 61

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------|----------|--|---------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4479 | 286N4479 | | | | E/E RACKS- (continued) | | | | | | | | | | | |
| 5013R | 24 | G2 | AM | | 0-0 | 34-22-28 | | D41565P | 35 | | | D41563P | 41 | | | 001-099 |
| 5013R | 24 | G2 | AM | | 0-0 | SPARE | | D41565P | 35 | | | D41563P | 41 | | | 115-199 |
| 5013Z | | | AM | | 0-0 | 34-22-28 | | D41565P | 37 | | | D41563P | 43 | | | 001-099 |
| 5013Z | | | AM | | 0-0 | SPARE | | D41565P | 37 | | | D41563P | 43 | | | 115-199 |
| 5014B | 24 | G2 | AN | | 9-0 | 34-22-29 | | D41567P | 8 | | | D41565P | 39 | | | ALL |
| 5014R | 24 | G2 | AN | | 0-0 | 34-22-29 | | D41567P | 7 | | | D41565P | 38 | | | ALL |
| 5014Z | | | AN | | 0-0 | 34-22-29 | | D41567P | 9 | | | D41565P | 40 | | | ALL |
| 5015B | 24 | 7K | AO | | 10-0 | 34-43-11 | | D41567P | 10 | | | D41563P | 45 | | | 001, 003-099 |
| 5015B | 24 | 7K | AO | | 10-0 | SPARE | | D41567P | 10 | | | D41563P | 45 | | | 002 |
| 5015B | 24 | 7K | AO | | 11-0 | 34-43-11 | | D41567P | 10 | | | D41563P | 45 | | | 115-199 |
| 5015W | 24 | 7K | AO | | 0-0 | 34-43-11 | | D41567P | 11 | | | D41563P | 46 | | | 001, 003-099, 115-199 |
| 5015W | 24 | 7K | AO | | 0-0 | SPARE | | D41567P | 11 | | | D41563P | 46 | | | 002 |
| 5015Z | | | AO | | 0-0 | 34-43-11 | | D41567P | 12 | | | D41563P | 44 | | | 001, 003-099, 115-199 |
| 5015Z | | | AO | | 0-0 | SPARE | | D41567P | 12 | | | D41563P | 44 | | | 002 |
| 5016B | 24 | G2 | AP | | 10-0 | 34-22-38 | | D41567P | 29 | | | D41569P | 23 | | | ALL |
| 5016R | 24 | G2 | AP | | 0-0 | 34-22-38 | | D41567P | 28 | | | D41569P | 22 | | | ALL |
| 5016Z | | | AP | | 0-0 | 34-22-38 | | D41567P | 30 | | | D41569P | 24 | | | ALL |
| 5017B | 24 | G2 | AQ | | 10-0 | 34-61-12 | | D41567P | 14 | | | D41563P | 48 | | | 001-099 |
| 5017B | 24 | G2 | AQ | | 11-0 | SPARE | | D41567P | 14 | | | D41563P | 48 | | | 115-199 |
| 5017R | 24 | G2 | AQ | | 0-0 | 34-61-12 | | D41567P | 13 | | | D41563P | 47 | | | 001-099 |
| 5017R | 24 | G2 | AQ | | 0-0 | SPARE | | D41567P | 13 | | | D41563P | 47 | | | 115-199 |
| 5017Z | | | AQ | | 0-0 | 34-61-12 | | D41567P | 15 | | | D41563P | 49 | | | 001-099 |
| 5017Z | | | AQ | | 0-0 | SPARE | | D41567P | 15 | | | D41563P | 49 | | | 115-199 |
| 5018B | 24 | G2 | AR | | 8-0 | 34-22-39 | | D41595P | 2 | | | D41567P | 17 | | | 001-099 |
| 5018B | 24 | G2 | AR | | 9-0 | 34-22-39 | | D41595P | 2 | | | D41567P | 17 | | | 115-199 |
| 5018R | 24 | G2 | AR | | 0-0 | 34-22-39 | | D41595P | 1 | | | D41567P | 16 | | | ALL |
| 5018Z | | | AR | | 0-0 | 34-22-39 | | D41595P | 3 | | | D41567P | 18 | | | ALL |
| 5019B | 24 | G2 | AS | | 8-0 | 34-22-39 | | D41595P | 5 | | | D41567P | 20 | | | 001-099 |
| 5019B | 24 | G2 | AS | | 9-0 | 34-22-39 | | D41595P | 5 | | | D41567P | 20 | | | 115-199 |
| 5019R | 24 | G2 | AS | | 0-0 | 34-22-39 | | D41595P | 4 | | | D41567P | 19 | | | ALL |
| 5019Z | | | AS | | 0-0 | 34-22-39 | | D41595P | 6 | | | D41567P | 21 | | | ALL |
| 5020B | 24 | G2 | AT | | 8-0 | 34-22-39 | | D41595P | 8 | | | D41567P | 23 | | | 001-099 |
| 5020B | 24 | G2 | AT | | 9-0 | 34-22-39 | | D41595P | 8 | | | D41567P | 23 | | | 115-199 |
| 5020R | 24 | G2 | AT | | 0-0 | 34-22-39 | | D41595P | 7 | | | D41567P | 22 | | | ALL |
| 5020Z | | | AT | | 0-0 | 34-22-39 | | D41595P | 9 | | | D41567P | 24 | | | ALL |
| 5021B | 24 | G2 | AU | | 8-0 | 34-21-11 | | D41595P | 10 | | | D41569P | 10 | | | 001-099 |
| 5021B | 24 | G2 | AU | | 9-0 | 34-21-11 | | D41595P | 10 | | | D41569P | 10 | | | 115-199 |
| 5021R | 24 | G2 | AU | | 0-0 | 34-21-11 | | D41595P | 11 | | | D41569P | 11 | | | ALL |
| 5021Z | | | AU | | 0-0 | 34-21-11 | | D41595P | 12 | | | D41569P | 12 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 62

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4479 | 286N4479 | | | E/E RACKS- (continued) | | | | | | | | | | | |
| 5022B | 24 | | G2 | AV | 8-0 | 34-21-11 | D41595P | | | | D41569P | 13 | | | 001-099 |
| 5022B | 24 | | G2 | AV | 9-0 | 34-21-11 | D41595P | | | | D41569P | 13 | | | 115-199 |
| 5022R | 24 | | G2 | AV | 0-0 | 34-21-11 | D41595P | | | | D41569P | 14 | | | ALL |
| 5022Z | | | | AV | 0-0 | 34-21-11 | D41595P | | | | D41569P | 15 | | | ALL |
| 5023B | 24 | | G2 | AX | 8-0 | 34-22-35 | D41595P | | | | D41567P | 26 | | | 001-099 |
| 5023B | 24 | | G2 | AX | 9-0 | 34-22-35 | D41595P | | | | D41567P | 26 | | | 115-199 |
| 5023R | 24 | | G2 | AX | 0-0 | 34-22-35 | D41595P | | | | D41567P | 25 | | | ALL |
| 5023Z | | | | AX | 0-0 | 34-22-35 | D41595P | | | | D41567P | 27 | | | ALL |
| 5024B | 24 | | G2 | AY | 9-0 | 22-12-11 | D41567P | | | | D41565P | 43 | | | ALL |
| 5024R | 24 | | G2 | AY | 0-0 | 22-12-11 | D41567P | | | | D41565P | 42 | | | ALL |
| 5024Z | | | | AY | 0-0 | 22-12-11 | D41567P | | | | D41565P | 44 | | | ALL |
| 5025B | 24 | | G2 | AZ | 6-0 | 22-12-11 | D41595P | | | | D41565P | 46 | | | 001-099 |
| 5025B | 24 | | G2 | AZ | 7-0 | 22-12-11 | D41595P | | | | D41565P | 46 | | | 115-199 |
| 5025R | 24 | | G2 | AZ | 0-0 | 22-12-11 | D41595P | | | | D41565P | 45 | | | ALL |
| 5025Z | | | | AZ | 0-0 | 22-12-11 | D41595P | | | | D41565P | 47 | | | ALL |
| 5026B | 24 | | G2 | BA | 8-0 | 22-13-11 | D41595P | | | | D41567P | 43 | | | 001-099 |
| 5026B | 24 | | G2 | BA | 9-0 | 22-13-11 | D41595P | | | | D41567P | 43 | | | 115-199 |
| 5026R | 24 | | G2 | BA | 0-0 | 22-13-11 | D41595P | | | | D41567P | 42 | | | ALL |
| 5026Z | | | | BA | 0-0 | 22-13-11 | D41595P | | | | D41567P | 44 | | | ALL |
| 5027B | 24 | | G2 | BB | 8-0 | 22-13-11 | D41595P | | | | D41569P | 17 | | | 001-099 |
| 5027B | 24 | | G2 | BB | 9-0 | 22-13-11 | D41595P | | | | D41569P | 17 | | | 115-199 |
| 5027R | 24 | | G2 | BB | 0-0 | 22-13-11 | D41595P | | | | D41569P | 16 | | | ALL |
| 5027Z | | | | BB | 0-0 | 22-13-11 | D41595P | | | | D41569P | 18 | | | ALL |
| 5028B | 24 | | G2 | BC | 7-0 | 22-15-11 | D41743P | | | | D41595P | 46 | | | 001-099 |
| 5028B | 24 | | G2 | BC | 10-0 | 22-15-11 | D41743P | | | | D41595P | 46 | | | 115-199 |
| 5028R | 24 | | G2 | BC | 0-0 | 22-15-11 | D41743P | | | | D41595P | 45 | | | ALL |
| 5028Z | | | | BC | 0-0 | 22-15-11 | D41743P | | | | D41595P | 47 | | | ALL |
| 5029B | 24 | | G2 | BD | 10-0 | 22-32-11 | D41817P | | | | D41819P | 3 | | | 001-099 |
| 5029B | 24 | | G2 | BD | 11-0 | 22-32-11 | D41817P | | | | D41819P | 3 | | | 115-199 |
| 5029R | 24 | | G2 | BD | 0-0 | 22-32-11 | D41817P | | | | D41819P | 2 | | | ALL |
| 5029Z | | | | BD | 0-0 | 22-32-11 | D41817P | | | | D41819P | 4 | | | ALL |
| 5030B | 24 | | G2 | BE | 10-0 | 22-32-11 | D41817P | | | | D41819P | 6 | | | 001-099 |
| 5030B | 24 | | G2 | BE | 11-0 | 22-32-11 | D41817P | | | | D41819P | 6 | | | 115-199 |
| 5030R | 24 | | G2 | BE | 0-0 | 22-32-11 | D41817P | | | | D41819P | 5 | | | ALL |
| 5030Z | | | | BE | 0-0 | 22-32-11 | D41817P | | | | D41819P | 7 | | | ALL |
| 5031B | 24 | | G2 | BF | 10-0 | 22-32-11 | D41569P | | | | D41819P | 9 | | | ALL |
| 5031R | 24 | | G2 | BF | 0-0 | 22-32-11 | D41569P | | | | D41819P | 8 | | | ALL |
| 5031Z | | | | BF | 0-0 | 22-32-11 | D41569P | | | | D41819P | 10 | | | ALL |
| 5033B | 24 | | G2 | AW | 10-0 | 34-22-19 | D41563P | | | | D41567P | 49 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 63

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4479 | 286N4479 | | | | E/E RACKS- (continued) | | | | | | | | | | |
| 5033B | 24 | G2 | BH | | 11-0 | 34-22-19 | D41563P | 52 | | | D41567P | 49 | | | 115-199 |
| 5033R | 24 | G2 | AW | | 0-0 | 34-22-19 | D41563P | 51 | | | D41567P | 48 | | | 001-099 |
| 5033R | 24 | G2 | BH | | 0-0 | 34-22-19 | D41563P | 51 | | | D41567P | 48 | | | 115-199 |
| 5033Z | | | AW | | 0-0 | 34-22-19 | D41563P | 53 | | | D41567P | 45 | | | 001-099 |
| 5033Z | | | BH | | 0-0 | 34-22-19 | D41563P | 53 | | | D41567P | 45 | | | 115-199 |
| 5034B | 24 | G2 | BG | | 9-0 | SPARE | D41817P | 24 | | | D41743P | 16 | | | 001-099 |
| 5034B | 24 | Y2 | BG | | 9-0 | 34-61-14 | D41817P | 24 | | | D41743P | 20 | | | 115-199 |
| 5034R | 24 | G2 | BG | | 0-0 | SPARE | D41817P | 23 | | | D41743P | 15 | | | 001-099 |
| 5034R | 24 | Y2 | BG | | 0-0 | 34-61-14 | D41817P | 23 | | | D41743P | 19 | | | 115-199 |
| 5034Z | | | BG | | 0-0 | SPARE | D41817P | 25 | | | D41743P | 17 | | | 001-099 |
| 5034Z | | | BG | | 0-0 | 34-61-14 | D41817P | 25 | | | D41743P | 21 | | | 115-199 |
| 5035B | 24 | G2 | BH | | 10-0 | SPARE | D41817P | 27 | | | D41819P | 12 | | | 001, 003-099 |
| 5035B | 24 | G2 | BH | | 10-0 | 34-46-14 | D41817P | 27 | | | D41819P | 12 | | | 002 |
| 5035B | 24 | G2 | BJ | | 13-0 | 34-58-11 | D41817P | 8 | | | D41819P | 19 | | | 115-199 |
| 5035R | 24 | G2 | BH | | 0-0 | SPARE | D41817P | 26 | | | D41819P | 11 | | | 001, 003-099 |
| 5035R | 24 | G2 | BH | | 0-0 | 34-46-14 | D41817P | 26 | | | D41819P | 11 | | | 002 |
| 5035R | 24 | G2 | BJ | | 0-0 | 34-58-11 | D41817P | 1 | | | D41819P | 18 | | | 115-199 |
| 5035Z | | | BH | | 0-0 | SPARE | D41817P | 28 | | | D41819P | 13 | | | 001, 003-099 |
| 5035Z | | | BH | | 0-0 | 34-46-14 | D41817P | 28 | | | D41819P | 13 | | | 002 |
| 5035Z | | | BJ | | 0-0 | 34-58-11 | D41817P | 31 | | | D41819P | 20 | | | 115-199 |
| 5038B | 24 | G2 | BK | | 10-0 | SPARE | D41569P | 26 | | | D41567P | 52 | | | 001-099 |
| 5038R | 24 | G2 | BK | | 0-0 | SPARE | D41569P | 25 | | | D41567P | 51 | | | 001-099 |
| 5038Z | | | BK | | 0-0 | SPARE | D41569P | 27 | | | D41567P | 53 | | | 001-099 |
| 5039B | 24 | G2 | BM | | 8-0 | 34-22-38 | D41819P | 16 | | | D41595P | 20 | | | 115-199 |
| 5039R | 24 | G2 | BM | | 0-0 | 34-22-38 | D41819P | 15 | | | D41595P | 19 | | | 115-199 |
| 5039Z | | | BM | | 0-0 | 34-22-38 | D41819P | 17 | | | D41595P | 21 | | | 115-199 |
| 5041B | 22 | GU | BO | | 14-0 | 34-25-12 | D41238P | 24 | | | D41819P | 22 | | | 002 |
| 5041R | 22 | GU | BO | | 0-0 | 34-25-12 | D41238P | 23 | | | D41819P | 21 | | | 002 |
| 5041Z | | | BO | | 0-0 | 34-25-12 | D41238P | 25 | | | D41819P | 23 | | | 002 |
| 5042B | 22 | GU | BS | | 14-0 | 34-25-12 | D41238P | 26 | | | D41819P | 19 | | | 002 |
| 5042R | 22 | GU | BS | | 0-0 | 34-25-12 | D41238P | 27 | | | D41819P | 18 | | | 002 |
| 5042Z | | | BS | | 0-0 | 34-25-12 | D41238P | 28 | | | D41819P | 20 | | | 002 |
| 5046B | 22 | GU | BI | | 10-0 | 34-58-21 | D41817P | 54 | | | D41565P | 50 | | | 115-199 |
| 5046R | 22 | GU | BI | | 0-0 | 34-58-21 | D41817P | 53 | | | D41565P | 49 | | | 115-199 |
| 5046Z | | | BI | | 0-0 | 34-58-21 | D41817P | 55 | | | D41565P | 51 | | | 115-199 |
| 5121B | 24 | G2 | BP | | 7-0 | 34-61-14 | D41743P | 30 | | | D41595P | 52 | | | 001-099 |
| 5121B | 22 | X2 | BP | | 9-0 | 34-61-14 | D41595P | 52 | | | D41743P | 16 | | | 115-199 |
| 5121R | 24 | G2 | BP | | 0-0 | 34-61-14 | D41743P | 29 | | | D41595P | 51 | | | 001-099 |
| 5121R | 22 | X2 | BP | | 0-0 | 34-61-14 | D41595P | 51 | | | D41743P | 18 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 64

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4479 | 286N4479 | | | E/E RACKS- (continued) | | | | | | | | | | | |
| 5121Z | | | | BP | 0-0 | 34-61-14 | D41743P | 31 | | | D41595P | 53 | | | 001-099 |
| 5121Z | | | | BP | 0-0 | 34-61-14 | D41595P | 43 | | | D41743P | 17 | | | 115-199 |
| 5186B | 24 | G2 | | LF | 7-0 | 34-22-28 | D41565P | 54 | | | D41595P | 54 | | | 115-199 |
| 5186R | 24 | G2 | | LF | 0-0 | 34-22-28 | D41565P | 53 | | | D41595P | 53 | | | 115-199 |
| 5186Z | | | | LF | 0-0 | 34-22-28 | D41565P | 55 | | | D41595P | 55 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4470

Page 65 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4481 | 286N4481 | | | E/E RACKS- | | | | | | | | | | | |
| 0001 | 24 | | GK | | 7-0 | 34-61-13 | D41603P | | 4 | | D41601P | | 4 | | 001-099 |
| 0001 | 24 | | GK | | 8-0 | 34-61-13 | D41603P | | 4 | | D41601P | | 4 | | 115-199 |
| 0002 | 24 | | GK | | 7-0 | 34-61-13 | D41603P | | 11 | | D41601P | | 11 | | 001-099 |
| 0002 | 24 | | GK | | 8-0 | 34-61-13 | D41603P | | 11 | | D41601P | | 11 | | 115-199 |
| 0003 | 24 | | GK | | 7-0 | 34-61-21 | D41603P | | 21 | | D41601P | | 21 | | 001-099 |
| 0003 | 24 | | GK | | 8-0 | 34-61-21 | D41603P | | 21 | | D41601P | | 21 | | 115-199 |
| 0004 | 24 | | GK | | 7-0 | 34-61-25 | D41601P | | 34 | | D41603P | | 34 | | 001-099 |
| 0004 | 24 | | GK | | 8-0 | 34-61-25 | D41601P | | 34 | | D41603P | | 34 | | 115-199 |
| 0005 | 24 | | GK | | 5-0 | 34-22-34 | D41603P | | 41 | | D41605P | | 1 | | 001-099 |
| 0005 | 24 | | GK | | 7-0 | 34-22-34 | D41603P | | 41 | | D41605P | | 1 | | 115-199 |
| 0006 | 24 | | GK | | 5-0 | 34-22-34 | D41603P | | 42 | | D41605P | | 2 | | 001-099 |
| 0006 | 24 | | GK | | 7-0 | 34-22-34 | D41603P | | 42 | | D41605P | | 2 | | 115-199 |
| 0007 | 24 | | GK | | 5-0 | 34-22-34 | D41603P | | 43 | | D41605P | | 3 | | 001-099 |
| 0007 | 24 | | GK | | 7-0 | 34-22-34 | D41603P | | 43 | | D41605P | | 3 | | 115-199 |
| 0008 | 24 | | GK | | 5-0 | 34-22-34 | D41603P | | 44 | | D41605P | | 4 | | 001-099 |
| 0008 | 24 | | GK | | 7-0 | 34-22-34 | D41603P | | 44 | | D41605P | | 4 | | 115-199 |
| 0009 | 24 | | GK | | 5-0 | 34-22-34 | D41603P | | 45 | | D41605P | | 5 | | 001-099 |
| 0009 | 24 | | GK | | 7-0 | 34-22-34 | D41603P | | 45 | | D41605P | | 5 | | 115-199 |
| 0010 | 24 | | GK | | 5-0 | 34-22-34 | D41603P | | 46 | | D41605P | | 6 | | 001-099 |
| 0010 | 24 | | GK | | 7-0 | 34-22-34 | D41603P | | 46 | | D41605P | | 6 | | 115-199 |
| 0011 | 24 | | GK | | 8-0 | 34-22-37 | D41605P | | 16 | | D41679P | | 7 | | 001-099 |
| 0011 | 24 | | GK | | 7-0 | 34-22-37 | D41605P | | 16 | | D41679P | | 7 | | 115-199 |
| 0012 | 24 | | GK | | 8-0 | 34-22-37 | D41605P | | 17 | | D41679P | | 8 | | 001-099 |
| 0012 | 24 | | GK | | 7-0 | 34-22-37 | D41605P | | 17 | | D41679P | | 8 | | 115-199 |
| 0013 | 24 | | GK | | 8-0 | 34-22-37 | D41605P | | 18 | | D41679P | | 9 | | 001-099 |
| 0013 | 24 | | GK | | 7-0 | 34-22-37 | D41605P | | 18 | | D41679P | | 9 | | 115-199 |
| 0014 | 24 | | GK | | 8-0 | 34-22-37 | D41605P | | 19 | | D41679P | | 10 | | 001-099 |
| 0014 | 24 | | GK | | 7-0 | 34-22-37 | D41605P | | 19 | | D41679P | | 10 | | 115-199 |
| 0015 | 24 | | GK | | 9-0 | 34-22-37 | D41605P | | 20 | | D41601P | | 38 | | 001-099 |
| 0015 | 24 | | GK | | 8-0 | 34-22-37 | D41605P | | 20 | | D41601P | | 38 | | 115-199 |
| 0016 | 24 | | GK | | 9-0 | 34-22-37 | D41605P | | 21 | | D41601P | | 39 | | 001-099 |
| 0016 | 24 | | GK | | 8-0 | 34-22-37 | D41605P | | 21 | | D41601P | | 39 | | 115-199 |
| 0017 | 24 | | GK | | 9-0 | 34-22-37 | D41605P | | 22 | | D41601P | | 40 | | 001-099 |
| 0017 | 24 | | GK | | 8-0 | 34-22-37 | D41605P | | 22 | | D41601P | | 40 | | 115-199 |
| 0018 | 24 | | GK | | 9-0 | 34-22-37 | D41605P | | 23 | | D41601P | | 41 | | 001-099 |
| 0018 | 24 | | GK | | 10-0 | 34-22-37 | D41605P | | 23 | | D41601P | | 41 | | 115-199 |
| 0019 | 24 | | GK | | 9-0 | SPARE | D41601P | | 42 | | D41605P | | 36 | | 001-099 |
| 0019 | 24 | | PK | | 11-0 | 34-22-37 | D41601P | | 42 | | D41605P | | 36 | | 115-199 |
| 0021 | 22 | | GA | | 9-0 | 22-14-21 | D41601P | | 44 | | D41679P | | 34 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4480

Page 1

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------|-------------|----|-------|-----|------------------------|----------|---------|------|------|--------|-------|---------|------|--------|-------------|--------------|--|
| | Wire No. | GA | CO TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4481 | 286N4481 | | | | E/E RACKS- (continued) | | | | | | | | | | | | |
| 0023 | 22 | GA | | | 9-0 | SPARE | D41601P | 43 | | | | D41679P | 36 | | | ALL | |
| 0025 | 24 | GK | | | 5-0 | SPARE | D41603P | 50 | | | | D41605P | 37 | | | 001-099 | |
| 0026 | 22 | GA | | | 8-0 | 22-14-21 | D41605P | 40 | | | | D41679P | 38 | | | 001-099 | |
| 0026 | 22 | GA | | | 7-0 | 22-14-21 | D41605P | 40 | | | | D41679P | 38 | | | 115-199 | |
| 0027 | 22 | GA | | | 8-0 | 22-15-12 | D41679P | 42 | | | | D41745P | 4 | | | ALL | |
| 0028 | 22 | GA | | | 8-0 | 22-15-12 | D41679P | 43 | | | | D41605P | 41 | | | 001-099 | |
| 0028 | 22 | GA | | | 7-0 | 22-15-12 | D41679P | 43 | | | | D41605P | 41 | | | 115-199 | |
| 0029 | 22 | CQ | | | 12-0 | 34-22-16 | D41601P | 1 | | | | D41605P | 39 | | | 002 | |
| 0030 | 22 | CQ | | | 12-0 | 34-22-26 | D41603P | 54 | | | | D41605P | 55 | | | 002 | |
| 0031 | 24 | GK | | | 6-0 | 34-12-22 | D41745P | 10 | | | | D41821P | 7 | | | ALL | |
| 0032 | 22 | GA | | | 8-0 | 22-14-21 | D41605P | 48 | | | | D41679P | 32 | | | 001-099 | |
| 0032 | 22 | GA | | | 7-0 | 22-14-21 | D41605P | 48 | | | | D41679P | 32 | | | 115-199 | |
| 0033 | 24 | GK | | | 6-0 | SPARE | D41745P | 11 | | | | D41821P | 8 | | | 115-199 | |
| 0034 | 24 | GK | | | 10-0 | SPARE | D41601P | 2 | | | | D41679P | 50 | | | 115-199 | |
| 0035 | 24 | GK | | | 7-0 | SPARE | D41603P | 31 | | | | D41601P | 3 | | | 001-099 | |
| 0035 | 24 | GK | | | 8-0 | SPARE | D41603P | 31 | | | | D41601P | 3 | | | 115-199 | |
| 0036 | 24 | GK | | | 8-0 | SPARE | D41679P | 51 | | | | D41745P | 12 | | | ALL | |
| 0037 | 24 | GK | | | 6-0 | SPARE | D41821P | 9 | | | | D41823P | 7 | | | 115-199 | |
| 0038 | 24 | GK | | | 8-0 | SPARE | D41605P | 49 | | | | D41679P | 52 | | | 001-099 | |
| 0038 | 24 | GK | | | 7-0 | 34-22-37 | D41605P | 49 | | | | D41679P | 52 | | | 115-199 | |
| 0039 | 24 | GK | | | 8-0 | SPARE | D41605P | 51 | | | | D41679P | 37 | | | 001, 003-099 | |
| 0039 | 24 | GK | | | 8-0 | SPARE | D41605P | REF | JB | | | D41679P | 37 | | | 002 | |
| 0039 | 24 | GK | | | 7-0 | SPARE | D41605P | 51 | | | | D41679P | 53 | | | 115-199 | |
| 0040 | 24 | GK | | | 7-0 | 34-22-16 | D41601P | 49 | | | | D41603P | 32 | | | 001-099 | |
| 0040 | 24 | GK | | | 8-0 | 34-22-16 | D41601P | 49 | | | | D41603P | 32 | | | 115-199 | |
| 0041 | 24 | GK | | | 9-0 | 34-22-16 | D41601P | 48 | | | | D41605P | 50 | | | 001-099 | |
| 0041 | 24 | GK | | | 8-0 | 34-22-16 | D41601P | 48 | | | | D41605P | 50 | | | 115-199 | |
| 0052 | 24 | GK | | | 9-0 | 34-22-16 | D41601P | 52 | | | | D41605P | 52 | | | 001-099 | |
| 0052 | 24 | GK | | | 8-0 | 34-22-16 | D41601P | 52 | | | | D41605P | 52 | | | 115-199 | |
| 0053 | 24 | GK | | | 5-0 | 34-22-26 | D41603P | 53 | | | | D41605P | 53 | | | 001-099 | |
| 0053 | 24 | GK | | | 7-0 | 34-22-26 | D41603P | 53 | | | | D41605P | 53 | | | 115-199 | |
| 0054 | 24 | GK | | | 8-0 | 34-22-37 | D41679P | 33 | | | | D41605P | 38 | | | 001-099 | |
| 0054 | 24 | GK | | | 7-0 | 34-22-37 | D41679P | 33 | | | | D41605P | 38 | | | 115-199 | |
| 0055 | 22 | CQ | | | 12-0 | 34-22-16 | D41601P | 2 | | | | D41605P | 54 | | | 002 | |
| 0056 | 22 | CQ | | | 12-0 | 34-22-26 | D41603P | 33 | | | | D41605P | 51 | | | 002 | |
| 5001B | 24 | G2 | AA | | 7-0 | SPARE | D41601P | 36 | | | | D41603P | 48 | | | 001-099 | |
| 5001R | 24 | G2 | AA | | 0-0 | SPARE | D41601P | 35 | | | | D41603P | 47 | | | 001-099 | |
| 5001Z | | | AA | | 0-0 | SPARE | D41601P | 37 | | | | D41603P | 49 | | | 001-099 | |
| 5002B | 24 | G2 | AB | | 7-0 | 34-61-13 | D41603P | 6 | | | | D41601P | 6 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4480

Page 2

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|-------------------------------|----------|---------|------|------|--------|---------|------|------|--------|--------------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4481 | 286N4481 | | | | E/E RACKS- (continued) | | | | | | | | | | |
| 5002B | 24 | | G2 | AB | 8-0 | 34-61-13 | D41603P | 6 | | | D41601P | 6 | | | 115-199 |
| 5002R | 24 | | G2 | AB | 0-0 | 34-61-13 | D41603P | 5 | | | D41601P | 5 | | | ALL |
| 5002Z | | | | AB | 0-0 | 34-61-13 | D41603P | 7 | | | D41601P | 7 | | | ALL |
| 5003B | 24 | | G2 | AC | 7-0 | 34-61-13 | D41603P | 9 | | | D41601P | 9 | | | 001-099 |
| 5003B | 24 | | G2 | AC | 8-0 | 34-61-13 | D41603P | 9 | | | D41601P | 9 | | | 115-199 |
| 5003R | 24 | | G2 | AC | 0-0 | 34-61-13 | D41603P | 8 | | | D41601P | 8 | | | ALL |
| 5003Z | | | | AC | 0-0 | 34-61-13 | D41603P | 10 | | | D41601P | 10 | | | ALL |
| 5004B | 24 | | G2 | AD | 7-0 | 34-61-13 | D41603P | 13 | | | D41601P | 13 | | | 001-099 |
| 5004B | 24 | | G2 | AD | 8-0 | 34-61-13 | D41603P | 13 | | | D41601P | 13 | | | 115-199 |
| 5004R | 24 | | G2 | AD | 0-0 | 34-61-13 | D41603P | 12 | | | D41601P | 12 | | | ALL |
| 5004Z | | | | AD | 0-0 | 34-61-13 | D41603P | 14 | | | D41601P | 14 | | | ALL |
| 5005B | 24 | | G2 | AE | 7-0 | 34-61-13 | D41603P | 16 | | | D41601P | 16 | | | 001-099 |
| 5005B | 24 | | G2 | AE | 8-0 | 34-61-13 | D41603P | 16 | | | D41601P | 16 | | | 115-199 |
| 5005R | 24 | | G2 | AE | 0-0 | 34-61-13 | D41603P | 15 | | | D41601P | 15 | | | ALL |
| 5005Z | | | | AE | 0-0 | 34-61-13 | D41603P | 17 | | | D41601P | 17 | | | ALL |
| 5006B | 24 | | G2 | AF | 7-0 | 34-61-21 | D41603P | 18 | | | D41601P | 18 | | | 001-099 |
| 5006B | 24 | | G2 | AF | 8-0 | 34-61-21 | D41603P | 18 | | | D41601P | 18 | | | 115-199 |
| 5006R | 24 | | G2 | AF | 0-0 | 34-61-21 | D41603P | 19 | | | D41601P | 19 | | | ALL |
| 5006Z | | | | AF | 0-0 | 34-61-21 | D41603P | 20 | | | D41601P | 20 | | | ALL |
| 5007B | 24 | | G2 | AG | 7-0 | 34-61-21 | D41603P | 23 | | | D41601P | 23 | | | 001-099 |
| 5007B | 24 | | G2 | AG | 8-0 | 34-61-21 | D41603P | 23 | | | D41601P | 23 | | | 115-199 |
| 5007R | 24 | | G2 | AG | 0-0 | 34-61-21 | D41603P | 24 | | | D41601P | 24 | | | ALL |
| 5007Z | | | | AG | 0-0 | 34-61-21 | D41603P | 22 | | | D41601P | 22 | | | ALL |
| 5008B | 24 | | G2 | AH | 7-0 | 34-61-21 | D41603P | 26 | | | D41601P | 26 | | | 001-099 |
| 5008B | 24 | | G2 | AH | 8-0 | 34-61-21 | D41603P | 26 | | | D41601P | 26 | | | 115-199 |
| 5008R | 24 | | G2 | AH | 0-0 | 34-61-21 | D41603P | 25 | | | D41601P | 25 | | | ALL |
| 5008Z | | | | AH | 0-0 | 34-61-21 | D41603P | 27 | | | D41601P | 27 | | | ALL |
| 5010B | 24 | | G2 | AJ | 7-0 | 34-61-22 | D41603P | 29 | | | D41601P | 29 | | | 001-099 |
| 5010B | 24 | | G2 | AJ | 8-0 | 34-61-22 | D41603P | 29 | | | D41601P | 29 | | | 115-199 |
| 5010R | 24 | | G2 | AJ | 0-0 | 34-61-22 | D41603P | 28 | | | D41601P | 28 | | | ALL |
| 5010Z | | | | AJ | 0-0 | 34-61-22 | D41603P | 30 | | | D41601P | 30 | | | ALL |
| 5011B | 24 | | G2 | AK | 6-0 | SPARE | D41821P | 14 | | | D41745P | 14 | | | 001, 003-099 |
| 5011B | 24 | | G2 | AK | 6-0 | SPARE | D41821P | 14 | | | D41745P | REF | JB | | 002 |
| 5011R | 24 | | G2 | AK | 0-0 | SPARE | D41821P | 13 | | | D41745P | 13 | | | 001, 003-099 |
| 5011R | 24 | | G2 | AK | 0-0 | SPARE | D41821P | 13 | | | D41745P | REF | JB | | 002 |
| 5011Z | | | | AK | 0-0 | SPARE | D41821P | 15 | | | D41745P | 15 | | | 001, 003-099 |
| 5011Z | | | | AK | 0-0 | SPARE | D41821P | 15 | | | D41745P | DED | | | 002 |
| 5012B | 24 | | G2 | AL | 7-0 | 34-22-18 | D41601P | 32 | | | D41603P | 2 | | | 001-099 |
| 5012B | 24 | | G2 | AL | 8-0 | SPARE | D41601P | 32 | | | D41603P | 2 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4480

Page 3

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | FT-IN | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|------------------------|----------|---------|-------|------|------|--------|---------|------|------|--------|-----------------------|
| | GA | CO | TY | | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W4481 | 286N4481 | | | E/E RACKS- (continued) | | | | | | | | | | | |
| 5012R | 24 | G2 | AL | 0-0 | 34-22-18 | D41601P | 31 | | | | D41603P | 1 | | | 001-099 |
| 5012R | 24 | G2 | AL | 0-0 | SPARE | D41601P | 31 | | | | D41603P | 1 | | | 115-199 |
| 5012Z | | | AL | 0-0 | 34-22-18 | D41601P | 33 | | | | D41603P | 3 | | | 001-099 |
| 5012Z | | | AL | 0-0 | SPARE | D41601P | 33 | | | | D41603P | 3 | | | 115-199 |
| 5013B | 24 | G2 | AM | 6-0 | SPARE | D41823P | 9 | | | | D41821P | 11 | | | 001, 003-099 |
| 5013B | 24 | G2 | AM | 6-0 | SPARE | D41823P | REF | JB | | | D41821P | 11 | | | 002 |
| 5013R | 24 | G2 | AM | 0-0 | SPARE | D41823P | 8 | | | | D41821P | 10 | | | 001, 003-099 |
| 5013R | 24 | G2 | AM | 0-0 | SPARE | D41823P | REF | JB | | | D41821P | 10 | | | 002 |
| 5013Z | | | AM | 0-0 | SPARE | D41823P | 10 | | | | D41821P | 12 | | | 001, 003-099 |
| 5013Z | | | AM | 0-0 | SPARE | D41823P | DED | | | | D41821P | 12 | | | 002 |
| 5014B | 24 | G2 | AN | 5-0 | 34-22-34 | D41603P | 39 | | | | D41605P | 8 | | | 001-099 |
| 5014B | 24 | G2 | AN | 7-0 | 34-22-34 | D41603P | 39 | | | | D41605P | 8 | | | 115-199 |
| 5014R | 24 | G2 | AN | 0-0 | 34-22-34 | D41603P | 38 | | | | D41605P | 7 | | | ALL |
| 5014Z | | | AN | 0-0 | 34-22-34 | D41603P | 40 | | | | D41605P | 9 | | | ALL |
| 5015B | 24 | 7K | AO | 8-0 | 34-43-11 | D41605P | 11 | | | | D41679P | 5 | | | 001, 003-099 |
| 5015B | 24 | 7K | AO | 8-0 | SPARE | D41605P | 11 | | | | D41679P | 5 | | | 002 |
| 5015B | 24 | 7K | AO | 7-0 | 34-43-11 | D41605P | 11 | | | | D41679P | 5 | | | 115-199 |
| 5015W | 24 | 7K | AO | 0-0 | 34-43-11 | D41605P | 10 | | | | D41679P | 6 | | | 001, 003-099, 115-199 |
| 5015W | 24 | 7K | AO | 0-0 | SPARE | D41605P | 10 | | | | D41679P | 6 | | | 002 |
| 5015Z | | | AO | 0-0 | 34-43-11 | D41605P | 12 | | | | D41679P | 4 | | | 001, 003-099, 115-199 |
| 5015Z | | | AO | 0-0 | SPARE | D41605P | 12 | | | | D41679P | 4 | | | 002 |
| 5016B | 24 | G2 | AP | 8-0 | 34-43-11 | D41605P | 15 | | | | D41679P | 2 | | | 001-099 |
| 5016B | 24 | G2 | AP | 7-0 | 34-43-11 | D41605P | 15 | | | | D41679P | 2 | | | 115-199 |
| 5016R | 24 | G2 | AP | 0-0 | 34-43-11 | D41605P | 14 | | | | D41679P | 3 | | | ALL |
| 5016Z | | | AP | 0-0 | 34-43-11 | D41605P | 13 | | | | D41679P | 1 | | | ALL |
| 5017B | 24 | G2 | AQ | 8-0 | 34-22-38 | D41605P | 25 | | | | D41679P | 12 | | | 001-099 |
| 5017B | 24 | G2 | AQ | 7-0 | SPARE | D41605P | 25 | | | | D41679P | 12 | | | 115-199 |
| 5017R | 24 | G2 | AQ | 0-0 | 34-22-38 | D41605P | 24 | | | | D41679P | 11 | | | 001-099 |
| 5017R | 24 | G2 | AQ | 0-0 | SPARE | D41605P | 24 | | | | D41679P | 11 | | | 115-199 |
| 5017Z | | | AQ | 0-0 | 34-22-38 | D41605P | 26 | | | | D41679P | 13 | | | 001-099 |
| 5017Z | | | AQ | 0-0 | SPARE | D41605P | 26 | | | | D41679P | 13 | | | 115-199 |
| 5018B | 24 | G2 | AR | 8-0 | 34-22-39 | D41605P | 29 | | | | D41679P | 16 | | | 001-099 |
| 5018B | 24 | G2 | AR | 7-0 | 34-22-39 | D41605P | 29 | | | | D41679P | 16 | | | 115-199 |
| 5018R | 24 | G2 | AR | 0-0 | 34-22-39 | D41605P | 28 | | | | D41679P | 15 | | | ALL |
| 5018Z | | | AR | 0-0 | 34-22-39 | D41605P | 27 | | | | D41679P | 14 | | | ALL |
| 5019B | 24 | G2 | AS | 8-0 | 34-22-39 | D41605P | 32 | | | | D41679P | 19 | | | 001-099 |
| 5019B | 24 | G2 | AS | 7-0 | 34-22-39 | D41605P | 32 | | | | D41679P | 19 | | | 115-199 |
| 5019R | 24 | G2 | AS | 0-0 | 34-22-39 | D41605P | 31 | | | | D41679P | 18 | | | ALL |
| 5019Z | | | AS | 0-0 | 34-22-39 | D41605P | 30 | | | | D41679P | 17 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4480

Page 4

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|------------------------|-------------|----------|---------|---------|------|--------|-------|---------|------|--------|--|-------------|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W4481 | 286N4481 | | | E/E RACKS- (continued) | | | | | | | | | | | | |
| 5020B | 24 | G2 | AT | | 8-0 | 34-22-39 | | D41605P | 35 | | | D41679P | 22 | | | 001-099 |
| 5020B | 24 | G2 | AT | | 7-0 | 34-22-39 | | D41605P | 35 | | | D41679P | 22 | | | 115-199 |
| 5020R | 24 | G2 | AT | | 0-0 | 34-22-39 | | D41605P | 34 | | | D41679P | 21 | | | ALL |
| 5020Z | | | AT | | 0-0 | 34-22-39 | | D41605P | 33 | | | D41679P | 20 | | | ALL |
| 5023B | 22 | X2 | AV | | 10-0 | 34-61-24 | | D41601P | 51 | | | D41679P | 29 | | | 115-199 |
| 5023R | 22 | X2 | AV | | 0-0 | 34-61-24 | | D41601P | 50 | | | D41679P | 28 | | | 115-199 |
| 5023Z | | | AV | | 0-0 | 34-61-24 | | D41601P | 1 | | | D41679P | 30 | | | 115-199 |
| 5025B | 24 | G2 | AY | | 8-0 | 22-15-11 | | D41679P | 40 | | | D41745P | 2 | | | ALL |
| 5025R | 24 | G2 | AY | | 0-0 | 22-15-11 | | D41679P | 39 | | | D41745P | 1 | | | ALL |
| 5025Z | | | AY | | 0-0 | 22-15-11 | | D41679P | 41 | | | D41745P | 3 | | | ALL |
| 5026B | 24 | G2 | AZ | | 8-0 | 22-12-21 | | D41679P | 45 | | | D41605P | 43 | | | 001-099 |
| 5026B | 24 | G2 | AZ | | 7-0 | 22-12-21 | | D41679P | 45 | | | D41605P | 43 | | | 115-199 |
| 5026R | 24 | G2 | AZ | | 0-0 | 22-12-21 | | D41679P | 44 | | | D41605P | 42 | | | ALL |
| 5026Z | | | AZ | | 0-0 | 22-12-21 | | D41679P | 46 | | | D41605P | 44 | | | ALL |
| 5027B | 24 | G2 | BA | | 8-0 | 22-12-21 | | D41679P | 47 | | | D41745P | 5 | | | ALL |
| 5027R | 24 | G2 | BA | | 0-0 | 22-12-21 | | D41679P | 48 | | | D41745P | 6 | | | ALL |
| 5027Z | | | BA | | 0-0 | 22-12-21 | | D41679P | 49 | | | D41745P | 7 | | | ALL |
| 5029B | 24 | G2 | BC | | 6-0 | 22-32-11 | | D41821P | 2 | | | D41823P | 2 | | | ALL |
| 5029R | 24 | G2 | BC | | 0-0 | 22-32-11 | | D41821P | 1 | | | D41823P | 1 | | | ALL |
| 5029Z | | | BC | | 0-0 | 22-32-11 | | D41821P | 3 | | | D41823P | 3 | | | ALL |
| 5030B | 24 | G2 | BD | | 6-0 | 22-32-11 | | D41821P | 5 | | | D41823P | 5 | | | ALL |
| 5030R | 24 | G2 | BD | | 0-0 | 22-32-11 | | D41821P | 4 | | | D41823P | 4 | | | ALL |
| 5030Z | | | BD | | 0-0 | 22-32-11 | | D41821P | 6 | | | D41823P | 6 | | | ALL |
| 5031B | 24 | G2 | BE | | 7-0 | 34-22-19 | | D41601P | 46 | | | D41603P | 36 | | | 001-099 |
| 5031B | 24 | G2 | BE | | 8-0 | 34-22-19 | | D41601P | 46 | | | D41603P | 36 | | | 115-199 |
| 5031R | 24 | G2 | BE | | 0-0 | 34-22-19 | | D41601P | 45 | | | D41603P | 35 | | | ALL |
| 5031Z | | | BE | | 0-0 | 34-22-19 | | D41601P | 47 | | | D41603P | 37 | | | ALL |
| 5032B | 22 | GU | ME | | 12-0 | 34-25-12 | | D41200P | 5 | | | D41745P | 14 | | | 002 |
| 5032R | 22 | GU | ME | | 0-0 | 34-25-12 | | D41200P | 4 | | | D41745P | 13 | | | 002 |
| 5032Z | | | ME | | 0-0 | 34-25-12 | | D41200P | 6 | | | D41745P | 15 | | | 002 |
| 5033B | 22 | GU | MB | | 12-0 | 34-25-12 | | D41200P | 8 | | | D41819P | 16 | | | 002 |
| 5033R | 22 | GU | MB | | 0-0 | 34-25-12 | | D41200P | 7 | | | D41819P | 15 | | | 002 |
| 5033Z | | | MB | | 0-0 | 34-25-12 | | D41200P | 9 | | | D41819P | 17 | | | 002 |
| 5034B | 22 | GU | MC | | 12-0 | 34-25-12 | | D41200P | 10 | | | D41823P | 8 | | | 002 |
| 5034R | 22 | GU | MC | | 0-0 | 34-25-12 | | D41200P | 11 | | | D41823P | 9 | | | 002 |
| 5034Z | | | MC | | 0-0 | 34-25-12 | | D41200P | 12 | | | D41823P | 10 | | | 002 |
| 5035B | 22 | GU | MD | | 12-0 | 34-25-12 | | D41200P | 2 | | | D41745P | 9 | | | 002 |
| 5035R | 22 | GU | MD | | 0-0 | 34-25-12 | | D41200P | 1 | | | D41745P | 8 | | | 002 |
| 5035Z | | | MD | | 0-0 | 34-25-12 | | D41200P | 3 | | | D41745P | 11 | | | 002 |

WIRE LIST

D280N032

91-21-11

Section W4480

Page 5

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4481 | 286N4481 | | | E/E RACKS- (continued) | | | | | | | | | | | |
| 5039B | 24 | | G2 | BM | 7-0 | 34-22-38 | D41605P | 46 | | | D41679P | 26 | | | 115-199 |
| 5039R | 24 | | G2 | BM | 0-0 | 34-22-38 | D41605P | 45 | | | D41679P | 25 | | | 115-199 |
| 5039Z | | | | BM | 0-0 | 34-22-38 | D41605P | 47 | | | D41679P | 27 | | | 115-199 |
| 5120B | 24 | | G2 | BN | 9-0 | 34-61-24 | D41601P | 54 | | | D41679P | 54 | | | 001-099 |
| 5120B | 22 | | X2 | AW | 10-0 | 34-61-24 | D41601P | 36 | | | D41679P | 24 | | | 115-199 |
| 5120R | 24 | | G2 | BN | 0-0 | 34-61-24 | D41601P | 53 | | | D41679P | 53 | | | 001-099 |
| 5120R | 22 | | X2 | AW | 0-0 | 34-61-24 | D41601P | 35 | | | D41679P | 23 | | | 115-199 |
| 5120Z | | | | BN | 0-0 | 34-61-24 | D41601P | 55 | | | D41679P | 55 | | | 001-099 |
| 5120Z | | | | AW | 0-0 | 34-61-24 | D41601P | 37 | | | D41679P | 31 | | | 115-199 |
| 5186B | 24 | | G2 | LF | 8-0 | 34-22-18 | D41601P | 54 | | | D41603P | 54 | | | 115-199 |
| 5186R | 24 | | G2 | LF | 0-0 | 34-22-18 | D41601P | 53 | | | D41603P | 52 | | | 115-199 |
| 5186Z | | | | LF | 0-0 | 34-22-18 | D41601P | 55 | | | D41603P | 55 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4480

Page 6 End

Oct 09/2008



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4500 | 286N4500 | | | P31 TO E/E SHELVES L GEN PWR CONTROL | | | | | | | | | | | |
| 0001 | 18 | | GA | | 25-0 | 24-22-11 | D40392P | | | 1 | D41742P | | | 1 | ALL |
| 0002 | 24 | | GK | | 25-0 | 24-22-11 | D40392P | | | 2 | D41742P | | | 9 | ALL |
| 0003 | 24 | | GK | | 25-0 | 24-28-11 | D40392P | | | 11 | D40542P | | | 11 | ALL |
| 0004 | 24 | | GK | | 25-0 | 24-27-11 | D40392P | | | 12 | D41742P | | | 19 | ALL |
| 0005 | 24 | | GK | | 25-0 | 24-27-11 | D40392P | | | 13 | D41742P | | | 20 | ALL |
| 0006 | 24 | | GK | | 25-0 | 24-22-12 | D40392P | | | 14 | D41742P | | | 21 | ALL |
| 0007 | 18 | | GA | | 25-0 | 24-22-12 | D40392P | | | 15 | D41742P | | | 4 | ALL |
| 0008 | 18 | | GA | | 25-0 | 24-21-11 | D40392P | | | 27 | D41742P | | | 8 | ALL |
| 0009 | 18 | | GA | | 25-0 | 24-21-11 | D40392P | | | 28 | D41742P | | | 6 | ALL |
| 0010 | 18 | | GA | | 25-0 | 24-21-11 | D40392P | | | 29 | D41742P | | | 10 | ALL |
| 0011 | 24 | | GK | | 18-0 | SPARE | D40542P | | | 14 | D41744P | | | 14 | 001-099 |
| 0012 | 20 | | GA | | 25-0 | 24-22-11 | D40392P | | | 31 | D41742P | | | 31 | ALL |
| 0013 | 20 | | GA | | 25-0 | 24-22-11 | D40392P | | | 32 | D41742P | | | 32 | ALL |
| 0014 | 20 | | GA | | 25-0 | 24-22-11 | D40392P | | | 33 | D41742P | | | 22 | ALL |
| 0015 | 20 | | GA | | 25-0 | 24-22-12 | D40392P | | | 34 | D41742P | | | 23 | ALL |
| 0016 | 20 | | GA | | 25-0 | 24-22-12 | D40392P | | | 35 | D41742P | | | 24 | ALL |
| 0017 | 20 | | GA | | 25-0 | 24-22-12 | D40392P | | | 36 | D41742P | | | 25 | ALL |
| 0018 | 20 | | GA | | 26-0 | 25-31-33 | D40392P | | | 22 | D41744P | | | 1 | ALL |
| 0019 | 24 | | GK | | 26-0 | 24-22-12 | D40392P | | | 20 | D41744P | | | 6 | ALL |
| 0020 | 24 | | GK | | 26-0 | 24-22-12 | D40392P | | | 21 | D41744P | | | 7 | 001-099 |
| 0020 | 24 | | GK | | 25-0 | 24-22-12 | D40392P | | | 21 | D41744P | | | 7 | 115-199 |
| 0021 | 22 | | GA | | 25-0 | SPARE | D40392P | | | 37 | D40542P | | | 1 | ALL |
| 0030 | 16 | | GA | | 25-0 | 29-11-22 | D40392P | | | 42 | D40542P | | | 2 | ALL |
| 0032 | 22 | | GA | | 25-0 | 29-11-31 | D40392P | | | 25 | D40542P | | | 6 | ALL |
| 0034 | 24 | | GK | | 25-0 | 24-22-12 | D40392P | | | 38 | D41742P | | | 2 | 001-099 |
| 0034 | 18 | | GA | | 25-0 | 24-22-12 | D40392P | | | 38 | D41742P | | | 2 | 115-199 |
| 0037 | 20 | | GA | | 17-0 | SPARE | D40542P | | | 7 | D41742P | | | 7 | 115-199 |
| 0601 | 20 | | GA | | 17-0 | SPARE | D40542P | | | 5 | D41742P | | | 26 | 115-199 |
| 0602 | 20 | | GA | | 17-0 | SPARE | D40542P | | | 8 | D41742P | | | 27 | 115-199 |
| 0603 | 20 | | GA | | 17-0 | SPARE | D40542P | | | 9 | D41742P | | | 28 | 115-199 |
| 0606 | 24 | | GK | | 18-0 | 24-22-22 | D40542P | | | 10 | D41744P | | | 10 | 001-099 |
| 0606 | 20 | | GA | | 18-0 | 24-22-22 | D40542P | | | 10 | D41744P | | | 10 | 115-199 |
| 0607 | 20 | | GA | | 18-0 | SPARE | D40542P | | | 12 | D41744P | | | 11 | 115-199 |
| 0608 | 20 | | GA | | 18-0 | SPARE | D40542P | | | 13 | D41744P | | | 12 | 115-199 |
| 0609 | 20 | | GA | | 25-0 | SPARE | D40392P | | | 23 | D40542P | | | 3 | 115-199 |
| 0610 | 20 | | GA | | 25-0 | SPARE | D40392P | | | 24 | D40542P | | | 4 | 115-199 |
| 0613 | 20 | | GA | | 26-0 | SPARE | D40392P | | | 39 | D41744P | | | 8 | ALL |
| 0614 | 20 | | GA | | 26-0 | SPARE | D40392P | | | 40 | D41744P | | | 9 | ALL |
| 0616 | 20 | | GA | | 25-0 | SPARE | D40392P | | | 26 | D41742P | | | 3 | ALL |

WIRE LIST

D280N032

91-21-11

Section W4500

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4500 | 286N4500 | | | P31 TO E/E SHELVES L GEN PWR CONTROL (continued) | | | | | | | | | | | |
| 0617 | 20 | | GA | | 25-0 | SPARE | D40392P | | 30 | | D41742P | | 5 | | ALL |
| 4001B | 24 | | GN | AA | 25-0 | 24-23-11 | D40392P | | 4 | | D41742P | | 12 | | ALL |
| 4001G | 24 | | GN | AA | 0-0 | 24-23-11 | D40392P | | 3 | | D41742P | | 11 | | ALL |
| 4001R | 24 | | GN | AA | 0-0 | 24-23-11 | D40392P | | 6 | | D41742P | | 14 | | ALL |
| 4001Y | 24 | | GN | AA | 0-0 | 24-23-11 | D40392P | | 5 | | D41742P | | 13 | | ALL |
| 4002B | 24 | | GN | BA | 25-0 | 24-23-11 | D40392P | | 8 | | D41742P | | 16 | | ALL |
| 4002G | 24 | | GN | BA | 0-0 | 24-23-11 | D40392P | | 7 | | D41742P | | 15 | | ALL |
| 4002R | 24 | | GN | BA | 0-0 | 24-23-11 | D40392P | | 10 | | D41742P | | 18 | | ALL |
| 4002Y | 24 | | GN | BA | 0-0 | 24-23-11 | D40392P | | 9 | | D41742P | | 17 | | ALL |
| 4003B | 24 | | GN | CA | 26-0 | 24-23-12 | D40392P | | 16 | | D41744P | | 2 | | ALL |
| 4003G | 24 | | GN | CA | 0-0 | 24-23-12 | D40392P | | 17 | | D41744P | | 3 | | ALL |
| 4003R | 24 | | GN | CA | 0-0 | 24-23-12 | D40392P | | 18 | | D41744P | | 4 | | ALL |
| 4003Y | 24 | | GN | CA | 0-0 | 24-23-12 | D40392P | | 19 | | D41744P | | 5 | | ALL |
| W4502 | 286N4502 | | | P32 TO E/E SHELVES R GEN PWR CONTROL | | | | | | | | | | | |
| 0003 | 24 | | GK | | 8-0 | 24-27-21 | D40394P | | 3 | | D41748P | | 3 | | ALL |
| 0004 | 24 | | GK | | 8-0 | 24-27-21 | D40394P | | 4 | | D41748P | | 4 | | ALL |
| 0005 | 24 | | GK | | 8-0 | 24-28-11 | D40394P | | 5 | | D41748P | | 13 | | ALL |
| 0006 | 20 | | GA | | 23-0 | 24-22-22 | D40394P | | 15 | | D40492P | | 15 | | ALL |
| 0007 | 20 | | GA | | 23-0 | 24-22-22 | D40394P | | 22 | | D40492P | | 22 | | ALL |
| 0008 | 24 | | GK | | 25-0 | 24-22-22 | D40394P | | 19 | | D41750P | | 14 | | 001-099 |
| 0008 | 24 | | GK | | 24-0 | 24-22-22 | D40394P | | 19 | | D41750P | | 14 | | 115-199 |
| 0009 | 24 | | GK | | 25-0 | 24-22-22 | D40394P | | 20 | | D41750P | | 13 | | 001-099 |
| 0009 | 20 | | GA | | 24-0 | 24-22-22 | D40394P | | 20 | | D41750P | | 13 | | 115-199 |
| 0010 | 24 | | GK | | 23-0 | 24-22-22 | D40394P | | 21 | | D40492P | | 21 | | ALL |
| 0011 | 24 | | GK | | 23-0 | 24-22-21 | D40394P | | 23 | | D40492P | | 23 | | ALL |
| 0012 | 20 | | GA | | 23-0 | 24-22-21 | D40394P | | 24 | | D40492P | | 24 | | ALL |
| 0013 | 20 | | GA | | 23-0 | 24-22-21 | D40394P | | 25 | | D40492P | | 25 | | ALL |
| 0014 | 22 | | GA | | 21-0 | 32-42-12 | D41748P | | 20 | | D40492P | | 7 | | 001-099 |
| 0015 | 22 | | GA | | 23-0 | 24-22-22 | D40394P | | 27 | | D40492P | | 27 | | ALL |
| 0016 | 24 | | GK | | 5-0 | 24-51-31 | D40394P | | 28 | | D41318P | | 18 | | 001-099 |
| 0016 | 20 | | GA | | 5-0 | 24-51-31 | D40394P | | 28 | | D41318P | | 18 | | 115-199 |
| 0017 | 24 | | GK | | 5-0 | 24-51-31 | D40394P | | 29 | | D41318P | | 19 | | 001-099 |
| 0017 | 20 | | GA | | 5-0 | 24-51-31 | D40394P | | 29 | | D41318P | | 19 | | 115-199 |
| 0018 | 24 | | GK | | 8-0 | 24-51-71 | D41748P | | 1 | | D40394P | | 30 | | ALL |
| 0019 | 24 | | GK | | 8-0 | 24-51-71 | D41748P | | 2 | | D40394P | | 31 | | ALL |
| 0020 | 22 | | GA | | 5-0 | 29-11-31 | D41318P | | 26 | | D40394P | | 43 | | ALL |
| 0022 | 22 | | GA | | 8-0 | SPARE | D41316P | | 21 | | D41748P | | 5 | | ALL |
| 0023 | 24 | | GK | | 5-0 | 24-27-11 | D40394P | | 41 | | D41318P | | 23 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4500

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4502 | 286N4502 | | | | P32 TO E/E SHELVES R GEN PWR CONTROL (continued) | | | | | | | | | | | |
| 0024 | 22 | | GA | | 21-0 | 32-42-12 | | D41748P | 21 | | | D40492P | 26 | | | 001-099 |
| 0025 | 24 | | GK | | 7-0 | 24-22-22 | | D40394P | 37 | | | D40956P | 1 | | | 001-099 |
| 0025 | 24 | | GK | | 8-0 | 24-22-22 | | D40394P | 37 | | | D40956P | 1 | | | 115-199 |
| 0026 | 24 | | GK | | 7-0 | 24-27-11 | | D40394P | 38 | | | D40956P | 2 | | | 001-099 |
| 0026 | 24 | | GK | | 8-0 | 24-27-11 | | D40394P | 38 | | | D40956P | 2 | | | 115-199 |
| 0027 | 24 | | GK | | 5-0 | 24-22-22 | | D40394P | 39 | | | D41318P | 1 | | | ALL |
| 0028 | 24 | | GK | | 5-0 | 24-22-22 | | D40394P | 40 | | | D41318P | 2 | | | ALL |
| 0029 | 22 | | GA | | 7-0 | SPARE | | D41318P | 21 | | | D40956P | 12 | | | 115-199 |
| 0030 | 20 | | GA | | 5-0 | 24-22-22 | | D40394P | 42 | | | D41318P | 4 | | | ALL |
| 0031 | 24 | | GK | | 10-0 | 24-51-71 | | D41748P | 8 | | | D41318P | 5 | | | ALL |
| 0032 | 24 | | GK | | 10-0 | 24-51-71 | | D41748P | 9 | | | D41318P | 6 | | | ALL |
| 0033 | 24 | | GK | | 12-0 | 24-51-71 | | D41748P | 10 | | | D40956P | 3 | | | ALL |
| 0034 | 18 | | GA | | 23-0 | 24-21-21 | | D41316P | 1 | | | D40492P | 1 | | | ALL |
| 0035 | 18 | | GA | | 23-0 | 24-21-21 | | D41316P | 2 | | | D40492P | 2 | | | ALL |
| 0036 | 18 | | GA | | 23-0 | 24-21-21 | | D41316P | 6 | | | D40492P | 4 | | | ALL |
| 0037 | 18 | | GA | | 23-0 | 24-22-22 | | D41316P | 4 | | | D40492P | 6 | | | ALL |
| 0038 | 18 | | GA | | 23-0 | 24-22-21 | | D41316P | 8 | | | D40492P | 8 | | | ALL |
| 0039 | 20 | | GA | | 5-0 | 25-31-11 | | D40394P | 45 | | | D41318P | 7 | | | 001-099 |
| 0039 | 22 | | GA | | 5-0 | SPARE | | D40394P | 45 | | | D41318P | 7 | | | 115-199 |
| 0040 | 22 | | GA | | 5-0 | 29-11-31 | | D41318P | 8 | | | D41316P | 14 | | | 001-099 |
| 0040 | 22 | | GA | | 4-0 | 29-11-31 | | D41318P | 8 | | | D41316P | 14 | | | 115-199 |
| 0041 | 22 | | GA | | 5-0 | 29-11-31 | | D41318P | 9 | | | D41316P | 7 | | | 001-099 |
| 0041 | 22 | | GA | | 4-0 | 29-11-31 | | D41318P | 9 | | | D41316P | 7 | | | 115-199 |
| 0042 | 20 | | GA | | 25-0 | SPARE | | D41750P | 16 | | | D40394P | 46 | | | 001-099 |
| 0042 | 20 | | GA | | 24-0 | SPARE | | D41750P | 16 | | | D40394P | 46 | | | 115-199 |
| 0043 | 20 | | GA | | 25-0 | SPARE | | D41750P | 17 | | | D40394P | 47 | | | 001-099 |
| 0043 | 20 | | GA | | 24-0 | 25-31-21 | | D41750P | 17 | | | D40394P | 47 | | | 115-199 |
| 0044 | 22 | | GA | | 7-0 | 33-27-11 | | D40394P | 51 | | | D40956P | 9 | | | 001-099 |
| 0044 | 22 | | GA | | 8-0 | 33-27-11 | | D40394P | 51 | | | D40956P | 9 | | | 115-199 |
| 0045 | 22 | | GA | | 7-0 | SPARE | | D40394P | 52 | | | D40956P | 10 | | | 001-099 |
| 0045 | 22 | | GA | | 8-0 | 33-27-11 | | D40394P | 52 | | | D40956P | 10 | | | 115-199 |
| 0046 | 22 | | GA | | 8-0 | SPARE | | D40394P | 53 | | | D41748P | 12 | | | 001-099 |
| 0046 | 22 | | GA | | 8-0 | 33-27-11 | | D40394P | 53 | | | D41748P | 12 | | | 115-199 |
| 0047 | 22 | | GA | | 7-0 | SPARE | | D40394P | 54 | | | D40956P | 11 | | | 001-099 |
| 0047 | 22 | | GA | | 8-0 | 33-27-11 | | D40394P | 54 | | | D40956P | 11 | | | 115-199 |
| 0048 | 22 | | GA | | 8-0 | 33-27-21 | | D40394P | 48 | | | D40956P | 13 | | | 115-199 |
| 0049 | 22 | | GA | | 8-0 | 33-27-21 | | D40394P | 49 | | | D40956P | 14 | | | 115-199 |
| 0050 | 22 | | GA | | 8-0 | 33-27-21 | | D41748P | 15 | | | D40394P | 50 | | | 115-199 |
| 0052 | 24 | | GK | | 7-0 | 24-27-21 | | D40956P | 4 | | | D41318P | 15 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4500

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|--|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4502 | 286N4502 | P32 TO E/E SHELVES R GEN PWR CONTROL (continued) | | | | | | | | | | | | | |
| 0053 | 24 | GK | | | 5-0 | 24-27-21 | D41316P | 26 | | | D41318P | 16 | | | 001-099 |
| 0053 | 24 | GK | | | 4-0 | 24-27-21 | D41316P | 26 | | | D41318P | 16 | | | 115-199 |
| 0054 | 20 | GA | | | 8-0 | 24-22-12 | D40956P | 5 | | | D41316P | 28 | | | 001-099 |
| 0054 | 20 | GA | | | 7-0 | 24-22-12 | D40956P | 5 | | | D41316P | 28 | | | 115-199 |
| 0055 | 24 | GK | | | 8-0 | 24-22-12 | D40956P | 6 | | | D41316P | 9 | | | 001-099 |
| 0055 | 24 | GK | | | 7-0 | 24-22-12 | D40956P | 6 | | | D41316P | 9 | | | 115-199 |
| 0056 | 24 | GK | | | 5-0 | 24-22-12 | D41318P | 13 | | | D41316P | 30 | | | 001-099 |
| 0056 | 24 | GK | | | 4-0 | 24-22-12 | D41318P | 13 | | | D41316P | 30 | | | 115-199 |
| 0057 | 24 | GK | | | 5-0 | 24-22-12 | D41318P | 12 | | | D41316P | 11 | | | 001-099 |
| 0057 | 24 | GK | | | 4-0 | 24-22-12 | D41318P | 12 | | | D41316P | 11 | | | 115-199 |
| 0058 | 20 | GA | | | 5-0 | 24-22-12 | D41318P | 11 | | | D41316P | 12 | | | 001-099 |
| 0058 | 20 | GA | | | 4-0 | 24-22-12 | D41318P | 11 | | | D41316P | 12 | | | 115-199 |
| 0059 | 24 | GK | | | 7-0 | 24-22-12 | D40956P | 7 | | | D41318P | 17 | | | ALL |
| 0060 | 20 | GA | | | 7-0 | 24-22-12 | D40956P | 8 | | | D41318P | 10 | | | ALL |
| 0061 | 24 | GK | | | 5-0 | 24-22-12 | D41318P | 20 | | | D41316P | 13 | | | 001-099 |
| 0061 | 24 | GK | | | 4-0 | 24-22-12 | D41318P | 20 | | | D41316P | 13 | | | 115-199 |
| 0062 | 16 | GA | | | 12-0 | SPARE | D40956P | 16 | 16 | | D41748P | 27 | | | ALL |
| 0063 | 20 | GA | | | 7-0 | 25-31-11 | D40956P | 21 | | | D41318P | 29 | | | 001-099 |
| 0065 | 20 | GA | | | 26-0 | 25-31-11 | D40394P | 36 | | | D41750P | 18 | | | 001-099 |
| 0067 | 24 | GK | | | 8-0 | 24-27-21 | D40394P | 34 | | | D41748P | 14 | | | 001-099 |
| 0067 | 24 | GK | | | 7-0 | 24-27-21 | D40394P | 34 | | | D41748P | 14 | | | 115-199 |
| 0085 | 22 | GA | | | 6-0 | 24-22-22 | D41318P | 25 | | | D40956P | 25 | | | 001-099 |
| 0085 | 22 | GA | | | 7-0 | 24-22-22 | D41318P | 25 | | | D40956P | 25 | | | 115-199 |
| 0088 | 24 | GK | | | 12-0 | SPARE | D40956P | 17 | | | D41748P | 16 | | | ALL |
| 0089 | 24 | GK | | | 10-0 | 24-51-71 | D41318P | 14 | | | D41748P | 18 | | | ALL |
| 0091 | 24 | GK | | | 10-0 | 24-27-11 | D41318P | 22 | | | D41748P | 17 | | | ALL |
| 0092 | 22 | GA | | | 5-0 | SPARE | D41318P | 24 | | | D41316P | 20 | | | 001-099 |
| 0092 | 22 | GA | | | 4-0 | SPARE | D41318P | 24 | | | D41316P | 20 | | | 115-199 |
| 0093 | 24 | GK | | | 8-0 | 24-51-71 | D40394P | 2 | | | D41748P | 19 | | | ALL |
| 0111 | 20 | GA | | | 25-0 | 24-22-11 | D41318P | 30 | | | D40492P | 3 | | | 001-099 |
| 0111 | 20 | GA | | | 24-0 | 24-22-11 | D41318P | 30 | | | D40492P | 3 | | | 115-199 |
| 0140 | 20 | GA | | | 7-0 | SPARE | D41318P | 27 | | | D40956P | 15 | | | 001-099 |
| 0142 | 20 | GA | | | 5-0 | SPARE | D40394P | 32 | | | D41318P | 28 | | | 001-099 |
| 0142 | 20 | GA | | | 8-0 | SPARE | D40394P | 32 | | | D41748P | 6 | | | 115-199 |
| 0144 | 20 | GA | | | 8-0 | 25-31-21 | D40394P | 33 | | | D41748P | 7 | | | 115-199 |
| 0211 | 22 | GA | | | 10-0 | SPARE | D41318P | 3 | | | D41748P | 11 | | | ALL |
| 0301 | 18 | GA | | | 23-0 | 25-29-11 | D41748P | 28 | | | D04262 | =P | D | | ALL |
| 0302 | 18 | GA | | | 3-0 | 25-29-11 | D04262 | =N | D | | GD01832 | AC.. | E | | ALL |
| 0303 | 18 | GA | | | 3-0 | 25-29-11 | D04262 | =G | D | | GD02542 | ST.. | E | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4500

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4502 | 286N4502 | | | | P32 TO E/E SHELVES R GEN PWR CONTROL (continued) | | | | | | | | | | | |
| 0601 | 22 | | GA | | 25-0 | SPARE | | D41750P | 26 | | | D40394P | 26 | | | 001-099 |
| 0601 | 22 | | GA | | 24-0 | SPARE | | D41750P | 26 | | | D40394P | 26 | | | 115-199 |
| 0602 | 22 | | GA | | 6-0 | SPARE | | D40492P | 28 | | | D41750P | 28 | | | 115-199 |
| 0603 | 22 | | GA | | 6-0 | SPARE | | D40492P | 29 | | | D41750P | 29 | | | 115-199 |
| 0604 | 24 | | GK | | 12-0 | 24-34-11 | | D41748P | 26 | | | D40956P | 26 | | | 001-099 |
| 0604 | 22 | | GA | | 12-0 | 24-34-11 | | D41748P | 26 | | | D40956P | 26 | | | 115-199 |
| 0605 | 22 | | GA | | 12-0 | SPARE | | D41748P | 29 | | | D40956P | 27 | | | ALL |
| 0606 | 22 | | GA | | 12-0 | SPARE | | D41748P | 30 | | | D40956P | 28 | | | ALL |
| 0607 | 22 | | GA | | 23-0 | SPARE | | D40492P | 5 | | | D41316P | 5 | | | ALL |
| 0608 | 22 | | GA | | 7-0 | SPARE | | D40956P | 22 | | | D41316P | 22 | | | 115-199 |
| 0609 | 22 | | GA | | 7-0 | SPARE | | D40956P | 23 | | | D41316P | 23 | | | 115-199 |
| 0610 | 22 | | GA | | 7-0 | SPARE | | D40956P | 24 | | | D41316P | 24 | | | 115-199 |
| 0611 | 22 | | GA | | 25-0 | SPARE | | D41318P | 31 | | | D40492P | 31 | | | 001-099 |
| 0611 | 22 | | GA | | 24-0 | SPARE | | D41318P | 31 | | | D40492P | 31 | | | 115-199 |
| 2504B | 24 | | G2 | BB | 6-0 | 24-22-22 | | D40492P | 19 | | | D41750P | 19 | | | ALL |
| 2504R | 24 | | G2 | BB | 0-0 | 24-22-22 | | D40492P | 20 | | | D41750P | 20 | | | ALL |
| 2504Z | | | | BB | 0-0 | 24-22-22 | | D40492P | 9 | | | D41750P | 21 | | | ALL |
| 4001B | 24 | | GN | AA | 25-0 | 24-23-12 | | D40394P | 6 | | | D41750P | 6 | | | 001-099 |
| 4001B | 24 | | GN | AA | 24-0 | 24-23-12 | | D40394P | 6 | | | D41750P | 6 | | | 115-199 |
| 4001G | 24 | | GN | AA | 0-0 | 24-23-12 | | D40394P | 7 | | | D41750P | 7 | | | ALL |
| 4001R | 24 | | GN | AA | 0-0 | 24-23-12 | | D40394P | 8 | | | D41750P | 8 | | | ALL |
| 4001Y | 24 | | GN | AA | 0-0 | 24-23-12 | | D40394P | 9 | | | D41750P | 9 | | | ALL |
| 4002B | 24 | | GN | BA | 23-0 | 24-23-11 | | D40394P | 11 | | | D40492P | 11 | | | ALL |
| 4002G | 24 | | GN | BA | 0-0 | 24-23-11 | | D40394P | 10 | | | D40492P | 10 | | | ALL |
| 4002R | 24 | | GN | BA | 0-0 | 24-23-11 | | D40394P | 13 | | | D40492P | 13 | | | ALL |
| 4002Y | 24 | | GN | BA | 0-0 | 24-23-11 | | D40394P | 12 | | | D40492P | 12 | | | ALL |
| 4003B | 24 | | GN | CA | 23-0 | 24-23-11 | | D40394P | 16 | | | D40492P | 16 | | | ALL |
| 4003G | 24 | | GN | CA | 0-0 | 24-23-11 | | D40394P | 14 | | | D40492P | 14 | | | ALL |
| 4003R | 24 | | GN | CA | 0-0 | 24-23-11 | | D40394P | 18 | | | D40492P | 18 | | | ALL |
| 4003Y | 24 | | GN | CA | 0-0 | 24-23-11 | | D40394P | 17 | | | D40492P | 17 | | | ALL |
| 5001B | 22 | | GU | BC | 21-0 | 32-42-11 | | D40492P | 30 | | | D41748P | 23 | | | 001-099 |
| 5001R | 22 | | GU | BC | 0-0 | 32-42-11 | | D40492P | 29 | | | D41748P | 22 | | | 001-099 |
| 5001Z | | | | BC | 0-0 | 32-42-11 | | D40492P | 32 | | | D41748P | 24 | | | 001-099 |
| W4504 | 286N4504 | | | | P34 TO E/E SHELVES APU/EXT PWR CONTROL | | | | | | | | | | | |
| 0001 | 18 | | GA | | 29-0 | 24-21-41 | | D41326P | 23 | 18 | | D42118P | 1 | | | 001-099 |
| 0001 | 18 | | GA | | 29-0 | 24-21-41 | | D41326P | 23 | 18 | | D41900P | 1 | 18 | | 115-199 |
| 0002 | 18 | | GA | | 29-0 | 24-21-41 | | D41326P | 15 | 18 | | D42118P | 2 | | | 001-099 |
| 0002 | 18 | | GA | | 29-0 | 24-21-41 | | D41326P | 15 | 18 | | D41900P | 8 | 18 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4500

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4504 | 286N4504 | | | P34 TO E/E SHELVES APU/EXT PWR CONTROL (continued) | | | | | | | | | | | |
| 0003 | 18 | | GA | | 29-0 | 24-21-41 | D41326P | 22 | 18 | | D42118P | 3 | | | 001-099 |
| 0003 | 18 | | GA | | 29-0 | 24-21-41 | D41326P | 22 | 18 | | D41900P | 14 | 18 | | 115-199 |
| 0004 | 18 | | GA | | 29-0 | 24-22-41 | D41326P | 27 | 18 | | D42118P | 4 | | | 001-099 |
| 0004 | 18 | | GA | | 29-0 | 24-22-41 | D41326P | 27 | 18 | | D41900P | 12 | 18 | | 115-199 |
| 0005 | 20 | | GA | | 29-0 | 24-22-41 | D40400P | 5 | | | D42118P | 5 | | | 001-099 |
| 0005 | 20 | | GA | | 28-0 | 24-22-41 | D40400P | 5 | | | D41900P | 5 | | | 115-199 |
| 0006 | 20 | | GA | | 29-0 | 24-22-41 | D40400P | 6 | | | D42118P | 6 | | | 001-099 |
| 0006 | 20 | | GA | | 28-0 | 24-22-41 | D40400P | 6 | | | D41900P | 6 | | | 115-199 |
| 0007 | 24 | | GK | | 29-0 | 24-22-41 | D40400P | 7 | | | D42118P | 7 | | | 001-099 |
| 0007 | 24 | | GK | | 28-0 | 24-22-41 | D40400P | 7 | | | D41900P | 7 | | | 115-199 |
| 0008 | 24 | | GK | | 11-0 | 24-28-11 | D40400P | 8 | | | D40978P | 8 | | | ALL |
| 0009 | 24 | | GK | | 11-0 | 24-28-11 | D40400P | 9 | | | D40978P | 7 | | | ALL |
| 0010 | 20 | | GA | | 29-0 | 24-22-41 | D41326P | 29 | 18 | | D42118P | 8 | | | 001-099 |
| 0010 | 18 | | GA | | 29-0 | 24-22-41 | D41326P | 29 | 18 | | D41900P | 10 | 18 | | 115-199 |
| 0011 | 24 | | GK | | 29-0 | 24-41-11 | D41326P | 30 | 18 | | D42118P | 14 | | | 001-099 |
| 0011 | 18 | | GA | | 29-0 | 24-41-11 | D41326P | 30 | 18 | | D41900P | 11 | 18 | | 115-199 |
| 0012 | 24 | | GK | | 31-0 | 24-27-41 | D41326P | 31 | | | D41900P | 44 | | | 001-099 |
| 0012 | 24 | | GK | | 29-0 | 24-27-41 | D41326P | 31 | | | D41900P | 44 | | | 115-199 |
| 0013 | 24 | | GK | | 30-0 | 24-27-41 | D40400P | 13 | | | D41900P | 13 | | | 001-099 |
| 0013 | 24 | | GK | | 28-0 | 24-27-41 | D40400P | 13 | | | D41900P | 13 | | | 115-199 |
| 0014 | 22 | | GA | | 29-0 | 33-31-31 | D40400P | 14 | | | D42118P | 15 | | | 001-099 |
| 0014 | 20 | | GA | | 28-0 | 33-31-31 | D40400P | 14 | | | D41900P | 45 | | | 115-199 |
| 0015 | 24 | | GK | | 29-0 | 24-22-41 | D40400P | 52 | | | D42118P | 9 | | | 001-099 |
| 0015 | 24 | | GK | | 28-0 | 24-22-41 | D40400P | 52 | | | D41900P | 19 | | | 115-199 |
| 0031 | 24 | | GK | | 30-0 | 24-41-11 | D40400P | 31 | | | D41900P | 31 | | | 001-099 |
| 0031 | 24 | | GK | | 28-0 | 24-41-11 | D40400P | 31 | | | D41900P | 31 | | | 115-199 |
| 0032 | 24 | | GK | | 30-0 | 24-41-11 | D40400P | 32 | | | D41900P | 32 | | | 001-099 |
| 0032 | 24 | | GK | | 28-0 | 24-41-11 | D40400P | 32 | | | D41900P | 32 | | | 115-199 |
| 0033 | 24 | | GK | | 30-0 | 24-41-11 | D40400P | 33 | | | D41900P | 33 | | | 001-099 |
| 0033 | 24 | | GK | | 28-0 | 24-41-11 | D40400P | 33 | | | D41900P | 33 | | | 115-199 |
| 0034 | 24 | | GK | | 30-0 | 24-41-11 | D40400P | 34 | | | D41900P | 34 | | | 001-099 |
| 0034 | 24 | | GK | | 28-0 | 24-41-11 | D40400P | 34 | | | D41900P | 34 | | | 115-199 |
| 0035 | 24 | | GK | | 30-0 | 24-41-11 | D40400P | 35 | | | D41900P | 35 | | | 001-099 |
| 0035 | 24 | | GK | | 28-0 | 24-41-11 | D40400P | 35 | | | D41900P | 35 | | | 115-199 |
| 0036 | 24 | | GK | | 30-0 | 24-41-11 | D40400P | 36 | | | D41900P | 36 | | | 001-099 |
| 0036 | 24 | | GK | | 28-0 | 24-41-11 | D40400P | 36 | | | D41900P | 36 | | | 115-199 |
| 0037 | 24 | | GK | | 30-0 | 24-41-11 | D40400P | 37 | | | D41900P | 37 | | | 001-099 |
| 0037 | 24 | | GK | | 28-0 | 24-41-11 | D40400P | 37 | | | D41900P | 37 | | | 115-199 |
| 0038 | 24 | | GK | | 30-0 | 24-41-11 | D40400P | 38 | | | D41900P | 38 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4500

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4504 | 286N4504 | | | P34 TO E/E SHELVES APU/EXT PWR CONTROL (continued) | | | | | | | | | | | |
| 0038 | 20 | | GA | | 28-0 | 24-41-11 | D40400P | 38 | | | D41900P | 38 | | | 115-199 |
| 0039 | 20 | | GA | | 30-0 | 24-41-11 | D40400P | 39 | | | D41900P | 39 | | | 001-099 |
| 0039 | 20 | | GA | | 28-0 | 24-41-11 | D40400P | 39 | | | D41900P | 39 | | | 115-199 |
| 0040 | 20 | | GA | | 30-0 | 24-51-51 | D40400P | 40 | | | D41900P | 41 | | | 001-099 |
| 0040 | 20 | | GA | | 28-0 | 24-51-51 | D40400P | 40 | | | D41900P | 41 | | | 115-199 |
| 0041 | 20 | | GA | | 30-0 | 24-51-61 | D40400P | 41 | | | D41900P | 3 | | | 001-099 |
| 0041 | 20 | | GA | | 28-0 | 24-51-61 | D40400P | 41 | | | D41900P | 3 | | | 115-199 |
| 0042 | 20 | | GA | | 30-0 | 24-51-61 | D40400P | 42 | | | D41900P | 2 | | | 001-099 |
| 0042 | 20 | | GA | | 28-0 | 24-51-61 | D40400P | 42 | | | D41900P | 2 | | | 115-199 |
| 0046 | 24 | | GK | | 30-0 | 24-41-12 | D40400P | 46 | | | D41900P | 9 | | | 001-099 |
| 0046 | 24 | | GK | | 28-0 | 24-41-12 | D40400P | 46 | | | D41900P | 9 | | | 115-199 |
| 0047 | 24 | | GK | | 11-0 | 24-27-41 | D40978P | 6 | | | D40400P | 47 | | | ALL |
| 0050 | 24 | | GK | | 11-0 | 24-41-12 | D40400P | 50 | | | D40978P | 2 | | | 115-199 |
| 0051 | 24 | | GK | | 11-0 | 24-41-12 | D40400P | 51 | | | D40978P | 1 | | | 115-199 |
| 0056 | 22 | | GA | | 29-0 | SPARE | D41900P | 48 | | | D41326P | 11 | | | 115-199 |
| 0057 | 24 | | GK | | 30-0 | 24-51-51 | D40400P | 3 | | | D41900P | 40 | | | 001-099 |
| 0057 | 24 | | GK | | 28-0 | 24-51-51 | D40400P | 3 | | | D41900P | 40 | | | 115-199 |
| 0058 | 24 | | GK | | 30-0 | 24-51-51 | D40400P | 4 | | | D41900P | 43 | | | 001-099 |
| 0058 | 20 | | GA | | 28-0 | 24-51-51 | D40400P | 4 | | | D41900P | 43 | | | 115-199 |
| 0059 | 20 | | GA | | 30-0 | 24-51-51 | D40400P | 2 | | | D41900P | 42 | | | 001-099 |
| 0059 | 24 | | GK | | 26-0 | 24-51-51 | D40978P | 9 | | | D41900P | 42 | | | 115-199 |
| 0060 | 22 | | GA | | 31-0 | SPARE | D41326P | 12 | | | D41900P | 47 | | | 001-099 |
| 0060 | 22 | | GA | | 29-0 | SPARE | D41326P | 12 | | | D41900P | 47 | | | 115-199 |
| 0061 | 18 | | GA | | 11-0 | SPARE | D40978P | 5 | | | D41326P | 28 | 18 | | 115-199 |
| 0062 | 18 | | GA | | 28-0 | SPARE | D40400P | 11 | 18 | | D41900P | 46 | 18 | | 115-199 |
| 0064 | 24 | | GK | | 11-0 | 38-32-21 | D41326P | 3 | | | D40978P | 3 | | | 001-099 |
| 0064 | 20 | | GA | | 11-0 | 38-32-21 | D41326P | 3 | | | D40978P | 3 | | | 115-199 |
| 0065 | 22 | | GA | | 11-0 | 33-31-11 | D41326P | 24 | | | D40978P | 4 | | | ALL |
| 0066 | 22 | | GA | | 11-0 | 33-26-11 | D41326P | 25 | | | D40978P | 12 | | | ALL |
| 0067 | 20 | | GA | | 11-0 | 24-51-51 | D40400P | 10 | | | D40978P | 10 | | | 115-199 |
| 0601 | 20 | | GA | | 31-0 | SPARE | D41900P | 49 | | | D41326P | 5 | | | 001-099 |
| 0601 | 20 | | GA | | 29-0 | SPARE | D41900P | 49 | | | D41326P | 5 | | | 115-199 |
| 0602 | 20 | | GA | | 29-0 | SPARE | D41900P | 50 | | | D41326P | 6 | | | 115-199 |
| 0603 | 20 | | GA | | 11-0 | SPARE | D40978P | 11 | | | D41326P | 7 | | | 115-199 |
| 0604 | 20 | | GA | | 11-0 | SPARE | D40978P | 13 | | | D41326P | 8 | | | 115-199 |
| 0605 | 20 | | GA | | 11-0 | SPARE | D40978P | 14 | | | D41326P | 9 | | | 115-199 |
| 0606 | 20 | | GA | | 30-0 | SPARE | D41900P | 51 | | | D40400P | 1 | | | 001-099 |
| 0606 | 20 | | GA | | 28-0 | SPARE | D41900P | 51 | | | D40400P | 1 | | | 115-199 |
| 0607 | 20 | | GA | | 30-0 | SPARE | D41900P | 52 | | | D40400P | 12 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4500

Page 7

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|---|-------|-------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4504 | 286N4504 | P34 TO E/E SHELVES APU/EXT PWR CONTROL (continued) | | | | | | | | | | | | | |
| 0607 | 20 | GA | | | 28-0 | SPARE | D41900P | 52 | | | D40400P | 12 | | | 115-199 |
| 0609 | 20 | GA | | | 11-0 | SPARE | D40978P | 16 | | | D40400P | 43 | | | ALL |
| 0610 | 20 | GA | | | 11-0 | 24-51-61 | D40978P | 17 | | | D40400P | 44 | | | ALL |
| 4001B | 24 | GN | AA | | 29-0 | 24-23-11 | D40400P | 15 | | | D42118P | 11 | | | 001-099 |
| 4001B | 24 | GN | AA | | 29-0 | 24-23-11 | D40400P | 15 | | | D41900P | 15 | | | 115-199 |
| 4001G | 24 | GN | AA | | 0-0 | 24-23-11 | D40400P | 16 | | | D42118P | 10 | | | 001-099 |
| 4001G | 24 | GN | AA | | 0-0 | 24-23-11 | D40400P | 16 | | | D41900P | 16 | | | 115-199 |
| 4001R | 24 | GN | AA | | 0-0 | 24-23-11 | D40400P | 17 | | | D42118P | 13 | | | 001-099 |
| 4001R | 24 | GN | AA | | 0-0 | 24-23-11 | D40400P | 17 | | | D41900P | 17 | | | 115-199 |
| 4001Y | 24 | GN | AA | | 0-0 | 24-23-11 | D40400P | 18 | | | D42118P | 12 | | | 001-099 |
| 4001Y | 24 | GN | AA | | 0-0 | 24-23-11 | D40400P | 18 | | | D41900P | 18 | | | 115-199 |
| 4002B | 24 | GN | AB | | 31-0 | 24-23-12 | D40400P | 19 | | | D41900P | 22 | | | 001-099 |
| 4002B | 24 | GN | AB | | 29-0 | 24-23-12 | D40400P | 19 | | | D41900P | 22 | | | 115-199 |
| 4002G | 24 | GN | AB | | 0-0 | 24-23-12 | D40400P | 20 | | | D41900P | 20 | | | ALL |
| 4002R | 24 | GN | AB | | 0-0 | 24-23-12 | D40400P | 21 | | | D41900P | 21 | | | ALL |
| 4002Y | 24 | GN | AB | | 0-0 | 24-23-12 | D40400P | 22 | | | D41900P | 4 | | | ALL |
| 4003B | 24 | GN | AC | | 31-0 | 24-23-12 | D40400P | 23 | | | D41900P | 23 | | | 001-099 |
| 4003B | 24 | GN | AC | | 29-0 | 24-23-12 | D40400P | 23 | | | D41900P | 23 | | | 115-199 |
| 4003G | 24 | GN | AC | | 0-0 | 24-23-12 | D40400P | 24 | | | D41900P | 24 | | | ALL |
| 4003R | 24 | GN | AC | | 0-0 | 24-23-12 | D40400P | 25 | | | D41900P | 25 | | | ALL |
| 4003Y | 24 | GN | AC | | 0-0 | 24-23-12 | D40400P | 26 | | | D41900P | 26 | | | ALL |
| 4004B | 24 | GN | AD | | 31-0 | 24-41-11 | D40400P | 27 | | | D41900P | 27 | | | 001-099 |
| 4004B | 24 | GN | AD | | 29-0 | 24-41-11 | D40400P | 27 | | | D41900P | 27 | | | 115-199 |
| 4004G | 24 | GN | AD | | 0-0 | 24-41-11 | D40400P | 28 | | | D41900P | 28 | | | ALL |
| 4004R | 24 | GN | AD | | 0-0 | 24-41-11 | D40400P | 29 | | | D41900P | 29 | | | ALL |
| 4004Y | 24 | GN | AD | | 0-0 | 24-41-11 | D40400P | 30 | | | D41900P | 30 | | | ALL |
| W4508 | 286N4508 | P31 TO P70 LEFT AC SUPPLY | | | | | | | | | | | | | |
| 0001 | 08 | HA | | | 14-0 | 24-51-11 | TB5031 | 1 | E | | TB5050 | 1 | E | | 001-099 |
| 0001 | 08 | HA | | | 13-0 | 24-51-11 | TB5031 | 1 | E | | TB5050 | 1 | E | | 115-199 |
| 0002 | 08 | HA | | | 14-0 | 24-51-11 | TB5031 | 2 | E | | TB5050 | 2 | E | | 001-099 |
| 0002 | 08 | HA | | | 13-0 | 24-51-11 | TB5031 | 2 | E | | TB5050 | 2 | E | | 115-199 |
| 0003 | 08 | HA | | | 15-0 | 24-51-11 | TB5031 | 3 | E | | TB5050 | 3 | E | | 001-099 |
| 0003 | 08 | HA | | | 13-0 | 24-51-11 | TB5031 | 3 | E | | TB5050 | 3 | E | | 115-199 |
| 0004 | 10 | GA | | | 14-0 | 24-51-14 | TB5031 | 4 | E | | TB5050 | 4 | E | | 001-099 |
| 0004 | 08 | HA | | | 13-0 | 24-51-14 | TB5031 | 4 | E | | TB5050 | 10 | E | | 115-199 |
| 0005 | 10 | GA | | | 14-0 | 24-51-14 | TB5031 | 5 | E | | TB5050 | 5 | E | | 001-099 |
| 0005 | 08 | HA | | | 13-0 | 24-51-14 | TB5031 | 5 | E | | TB5050 | 11 | E | | 115-199 |
| 0006 | 10 | GA | | | 15-0 | 24-51-14 | TB5031 | 6 | E | | TB5050 | 6 | E | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4500

Page 8

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|--------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4508 | 286N4508 | | | P31 TO P70 LEFT AC SUPPLY (continued) | | | | | | | | | | | |
| 0006 | 08 | | HA | | 13-0 | 24-51-14 | TB5031 | 6 | E | | TB5050 | 12 | E | | 115-199 |
| 0007 | 10 | | HA | | 13-0 | 24-51-14 | TB5031 | 7 | E | | K10297 | A1 | E | | 115-199 |
| 0008 | 10 | | HA | | 13-0 | 24-51-14 | TB5031 | 8 | E | | K10297 | B1 | E | | 115-199 |
| 0009 | 10 | | HA | | 13-0 | 24-51-14 | TB5031 | 9 | E | | K10297 | C1 | E | | 115-199 |

WIRE LIST
D280N032

91-21-11
Section W4500
Page 9 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | To | | | Effectivity | | | |
|------------------------|-------------|----|----|-----|----------------------------------|----------|---------|------|------|--------|-------|---------|------|-------------|--------|---------|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | | Splice | | |
| W4510 | 286N4510 | | | | P32 TO P37 RIGHT AC SUPPLY | | | | | | | | | | | | |
| 0001 | 08 | HA | | | 10-0 | 24-51-21 | TB5070 | | 4 | E | | TB5032 | 4 | E | | 001-099 | |
| 0001 | 08 | HA | | | 9-9 | 24-51-21 | TB5070 | | 4 | E | | TB5032 | 4 | E | | 115-199 | |
| 0002 | 08 | HA | | | 10-0 | 24-51-21 | TB5070 | | 5 | E | | TB5032 | 5 | E | | 001-099 | |
| 0002 | 08 | HA | | | 9-5 | 24-51-21 | TB5070 | | 5 | E | | TB5032 | 5 | E | | 115-199 | |
| 0003 | 08 | HA | | | 10-0 | 24-51-21 | TB5070 | | 6 | E | | TB5032 | 6 | E | | 001-099 | |
| 0003 | 08 | HA | | | 9-2 | 24-51-21 | TB5070 | | 6 | E | | TB5032 | 6 | E | | 115-199 | |
| 0004 | 08 | HA | | | 12-0 | 24-51-52 | K00102 | | A3 | F | | TB5032 | 1 | E | | 001-099 | |
| 0004 | 08 | HA | | | 9-4 | 24-51-52 | K00102 | | A3 | F | | TB5032 | 1 | E | | 115-199 | |
| 0005 | 08 | HA | | | 12-0 | 24-51-52 | K00102 | | B3 | F | | TB5032 | 2 | E | | 001-099 | |
| 0005 | 08 | HA | | | 10-2 | 24-51-52 | K00102 | | B3 | F | | TB5032 | 2 | E | | 115-199 | |
| 0006 | 08 | HA | | | 12-0 | 24-51-52 | K00102 | | C3 | F | | TB5032 | 3 | E | | 001-099 | |
| 0006 | 08 | HA | | | 9-0 | 24-51-52 | K00102 | | C3 | F | | TB5032 | 3 | E | | 115-199 | |
| 0007 | 10 | GA | | | 9-0 | 24-51-24 | K00120 | | A1 | E | | TB5032 | 7 | E | | 001-099 | |
| 0007 | 08 | HA | | | 8-9 | 24-51-24 | K00120 | | A1 | E | | TB5032 | 7 | E | | 115-199 | |
| 0008 | 10 | GA | | | 9-0 | 24-51-24 | K00120 | | B1 | E | | TB5032 | 8 | E | | 001-099 | |
| 0008 | 08 | HA | | | 8-6 | 24-51-24 | K00120 | | B1 | E | | TB5032 | 8 | E | | 115-199 | |
| 0009 | 10 | GA | | | 9-0 | 24-51-24 | K00120 | | C1 | E | | TB5032 | 9 | E | | 001-099 | |
| 0009 | 08 | HA | | | 8-5 | 24-51-24 | K00120 | | C1 | E | | TB5032 | 9 | E | | 115-199 | |
| 0010 | 08 | HA | | | 10-0 | 24-51-24 | K10298 | | A1 | E | | TB5032 | 10 | E | | 001-099 | |
| 0011 | 08 | HA | | | 10-0 | 24-51-24 | K10298 | | B1 | E | | TB5032 | 11 | E | | 001-099 | |
| 0011 | 10 | GA | | | 9-4 | 24-51-24 | K10298 | | A1 | E | | TB5032 | 10 | E | | 115-199 | |
| 0012 | 08 | HA | | | 10-0 | 24-51-24 | K10298 | | C1 | E | | TB5032 | 12 | E | | 001-099 | |
| 0012 | 10 | GA | | | 9-0 | 24-51-24 | K10298 | | B1 | E | | TB5032 | 11 | E | | 115-199 | |
| 0013 | 10 | GA | | | 8-10 | 24-51-24 | K10298 | | C1 | E | | TB5032 | 12 | E | | 115-199 | |
| 0014 | 14 | GA | | | 17-0 | 24-53-51 | D40496P | | 24 | | | T00126 | HV | E | | 001-099 | |
| 0017 | 08 | HA | | | 16-0 | 24-51-52 | K00102 | | A2 | F | | TB5070 | 7 | E | | 001-099 | |
| 0018 | 08 | HA | | | 16-0 | 24-51-52 | K00102 | | B2 | F | | TB5070 | 8 | E | | 001-099 | |
| 0019 | 08 | HA | | | 16-0 | 24-51-52 | K00102 | | C2 | F | | TB5070 | 9 | E | | 001-099 | |
| W4512 | 286N4512 | | | | P34 TO P37 GROUND SERVICE SUPPLY | | | | | | | | | | | | |
| 0001 | 08 | HA | | | 14-8 | 24-51-52 | K00103 | | A2 | F | | K00102 | A1 | F | | 115-199 | |
| 0002 | 08 | HA | | | 14-0 | 24-51-52 | K00103 | | B2 | F | | K00102 | B1 | F | | 115-199 | |
| 0003 | 08 | HA | | | 14-0 | 24-51-52 | K00103 | | C2 | F | | K00102 | C1 | F | | 115-199 | |
| 0004 | 06 | CQ | | | 14-1 | 24-53-51 | T00126 | | LV | E | | TB5034 | 1 | E | | 115-199 | |
| W4515 | 286N4515 | | | | E/E BAY TO E6 (LEFT) | | | | | | | | | | | | |
| 0001 | 24 | GK | | | 123-0 | 34-57-11 | D45001P | | 1 | | | D45003P | 1 | | | 001-099 | |
| 0002 | 24 | GK | | | 123-0 | SPARE | D45001P | | 2 | | | D45003P | 2 | | | 001-099 | |
| 2501B | 24 | G2 | AA | | 123-0 | 23-51-13 | D45001P | | 3 | | | D45003P | 3 | | | 001-099 | |

WIRE LIST

D280N032

91-21-11

Section W4510

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4515 | 286N4515 | | | E/E BAY TO E6 (LEFT) (continued) | | | | | | | | | | | |
| 2501R | 24 | | G2 | AA | 0-0 | 23-51-13 | D45001P | | 4 | | D45003P | | 4 | | 001-099 |
| 2501Z | | | | AA | 0-0 | 23-51-13 | D45001P | | 5 | | D45003P | | 5 | | 001-099 |
| 2502B | 24 | | G2 | AB | 123-0 | SPARE | D45001P | | 6 | | D45003P | | 6 | | 001-099 |
| 2502R | 24 | | G2 | AB | 0-0 | SPARE | D45001P | | 7 | | D45003P | | 7 | | 001-099 |
| 2502Z | | | | AB | 0-0 | SPARE | D45001P | | 8 | | D45003P | | 8 | | 001-099 |
| 5002B | 24 | | G2 | AD | 123-0 | 34-22-81 | D45001P | | 12 | | D45003P | | 12 | | 001-099 |
| 5002R | 24 | | G2 | AD | 0-0 | 34-22-81 | D45001P | | 13 | | D45003P | | 13 | | 001-099 |
| 5002Z | | | | AD | 0-0 | 34-22-81 | D45001P | | 14 | | D45003P | | 14 | | 001-099 |
| 5003B | 24 | | G2 | AE | 123-0 | SPARE | D45001P | | 15 | | D45003P | | 15 | | 001-099 |
| 5003R | 24 | | G2 | AE | 0-0 | SPARE | D45001P | | 16 | | D45003P | | 16 | | 001-099 |
| 5003Z | | | | AE | 0-0 | SPARE | D45001P | | 17 | | D45003P | | 17 | | 001-099 |
| W4517 | 286N4517 | | | E/E BAY TO E6 (RIGHT) | | | | | | | | | | | |
| 0001 | 24 | | GK | | 127-0 | 34-57-21 | D45005P | | 1 | | D45007P | | 1 | | 001-099 |
| 0002 | 24 | | GK | | 127-0 | SPARE | D45005P | | 2 | | D45007P | | 2 | | 001-099 |
| 2501B | 24 | | G2 | AA | 127-0 | 23-51-13 | D45005P | | 3 | | D45007P | | 3 | | 001-099 |
| 2501R | 24 | | G2 | AA | 0-0 | 23-51-13 | D45005P | | 4 | | D45007P | | 4 | | 001-099 |
| 2501Z | | | | AA | 0-0 | 23-51-13 | D45005P | | 5 | | D45007P | | 5 | | 001-099 |
| 2502B | 24 | | G2 | AB | 127-0 | SPARE | D45005P | | 6 | | D45007P | | 6 | | 001-099 |
| 2502R | 24 | | G2 | AB | 0-0 | SPARE | D45005P | | 7 | | D45007P | | 7 | | 001-099 |
| 2502Z | | | | AB | 0-0 | SPARE | D45005P | | 8 | | D45007P | | 8 | | 001-099 |
| 5002B | 24 | | G2 | AD | 127-0 | 34-22-91 | D45005P | | 12 | | D45007P | | 12 | | 001-099 |
| 5002R | 24 | | G2 | AD | 0-0 | 34-22-91 | D45005P | | 13 | | D45007P | | 13 | | 001-099 |
| 5002Z | | | | AD | 0-0 | 34-22-91 | D45005P | | 14 | | D45007P | | 14 | | 001-099 |
| 5003B | 24 | | G2 | AE | 127-0 | SPARE | D45005P | | 15 | | D45007P | | 15 | | 001-099 |
| 5003R | 24 | | G2 | AE | 0-0 | SPARE | D45005P | | 16 | | D45007P | | 16 | | 001-099 |
| 5003Z | | | | AE | 0-0 | SPARE | D45005P | | 17 | | D45007P | | 17 | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W4510

Page 2 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--------------------------------|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4607 | 286N4607 | | | TCAS TO ATC SUPPRESSION | | | | | | | | | | | |
| 001CO | | | | AA | 0-0 | 34-45-02 | D41203P | = C1 | | | D41199P | = C1 | | | ALL |
| 001CX | | 66 | | AA | 16-2 | 34-45-02 | D41203P | = A1 | | | D41199P | = A1 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W4600

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | To | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|--------|------|------|--------|---------|------|-------------|---------|--------|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | | Type | Splice |
| W4900 | 286N4900 | | | | MN LNDG GEAR FWD JCTN BOX TO BRAKE TEMP SENSOR - RIGHT | | | | | | | | | | |
| 4501G | 18 | UY | TA | | 4-0 | 32-46-11 | D02656 | 3 | 4H | | TB0211K | A002 | 1 | 115-199 | |
| 4501W | 18 | UY | TA | | 0-0 | 32-46-11 | D02656 | 1 | 4L | | TB0211K | E002 | 1 | 115-199 | |
| W4902 | 286N4902 | | | | MN LNDG GEAR AFT JCTN BOX TO BRAKE TEMP SENSOR - RIGHT | | | | | | | | | | |
| 4501G | 18 | UY | TA | | 4-0 | 32-46-11 | D02660 | 3 | 4H | | TB0212K | C001 | 1 | 115-199 | |
| 4501W | 18 | UY | TA | | 0-0 | 32-46-11 | D02660 | 1 | 4L | | TB0212K | A001 | 1 | 115-199 | |
| W4904 | 286N4904 | | | | MN LNDG GEAR FWD JCTN BOX TO ANTI-SKID SENSORS - RIGHT | | | | | | | | | | |
| 2501B | 20 | HQ | AA | | 3-10 | 32-42-11 | D02040 | 3 | | | TB0211K | E003 | 1 | ALL | |
| 2501R | 20 | HQ | AA | | 0-0 | 32-42-11 | D02040 | 1 | | | TB0211K | G003 | 1 | ALL | |
| 2501Z | | | AA | | 0-0 | 32-42-11 | D02040 | DED | | | TB0211L | A004 | 1 | ALL | |
| 2502B | 20 | HQ | AB | | 3-10 | 32-42-11 | D02042 | 3 | | | TB0211K | A003 | 1 | ALL | |
| 2502R | 20 | HQ | AB | | 0-0 | 32-42-11 | D02042 | 1 | | | TB0211K | C003 | 1 | ALL | |
| 2502Z | | | AB | | 0-0 | 32-42-11 | D02042 | DED | | | TB0211L | E004 | 1 | ALL | |
| W4906 | 286N4906 | | | | MN LNDG GEAR FWD JCTN BOX TO SYS 1 TRUCK TILT PROX SENSORS - RIGHT | | | | | | | | | | |
| 3001B | 20 | HN | AA | | 10-0 | 27-62-11 | D04201 | C | | | TB0211K | C002 | 1 | ALL | |
| 3001R | 20 | HN | AA | | 0-0 | 27-62-11 | D04201 | A | | | TB0211K | G002 | 1 | ALL | |
| 3001Y | 20 | HN | AA | | 0-0 | 27-62-11 | D04201 | B | | | TB0211K | A002 | 1 | 001-099 | |
| 3001Y | 20 | HN | AA | | 0-0 | 27-62-11 | D04201 | B | | | TB0211K | C005 | 1 | 115-199 | |
| A-AA | | | | | 0-0 | 32-09-11 | S10060 | BLU | | | TB0211K | G001 | 1 | ALL | |
| A-AB | | | | | 0-0 | 32-09-11 | S10060 | RED | | | TB0211K | E001 | 1 | ALL | |

WIRE LIST

D280N032

91-21-11
Section W4900
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | Effectivity | |
|------------|-------------|----|-------|--|---------|----------|---------|-------|------|------|---------|-------|------|-------------|---------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | | Type |
| W4910 | 286N4910 | | | MN LNDG GEAR - WING/TRUCK DISC TO FWD JCTN BOX - RIGHT | | | | | | | | | | | |
| 2001B | 18 | HM | CC | | 22-0 | 32-09-11 | D40442P | 12 | | | TB0211K | G001 | 1 | | 001-099 |
| 2001B | 18 | HM | CC | | 17-0 | 32-09-11 | D40442P | 12 | | | TB0211K | G001 | 1 | | 115-199 |
| 2001R | 18 | HM | CC | | 0-0 | 32-09-11 | D40442P | 11 | | | TB0211K | E001 | 1 | | ALL |
| 2501B | 20 | HQ | AA | | 22-0 | 32-42-11 | D40442P | 9 | | | TB0211K | E003 | 1 | | 001-099 |
| 2501B | 20 | HQ | AA | | 17-0 | 32-42-11 | D40442P | 9 | | | TB0211K | E003 | 1 | | 115-199 |
| 2501R | 20 | HQ | AA | | 0-0 | 32-42-11 | D40442P | 10 | | | TB0211K | G003 | 1 | | ALL |
| 2501Z | | | AA | | 0-0 | 32-42-11 | D40442P | 7 | | | TB0211L | A004 | 1 | | ALL |
| 2502B | 20 | HQ | AB | | 22-0 | 32-42-11 | D40442P | 3 | | | TB0211K | A003 | 1 | | 001-099 |
| 2502B | 20 | HQ | AB | | 17-0 | 32-42-11 | D40442P | 3 | | | TB0211K | A003 | 1 | | 115-199 |
| 2502R | 20 | HQ | AB | | 0-0 | 32-42-11 | D40442P | 4 | | | TB0211K | C003 | 1 | | ALL |
| 2502Z | | | AB | | 0-0 | 32-42-11 | D40442P | 5 | | | TB0211L | E004 | 1 | | ALL |
| 3001B | 20 | HN | AC | | 25-0 | 27-62-11 | D40442P | 15 | | | TB0211K | C002 | 1 | | ALL |
| 3001R | 20 | HN | AC | | 0-0 | 27-62-11 | D40442P | 16 | | | TB0211K | G002 | 1 | | ALL |
| 3001Y | 20 | HN | AC | | 0-0 | 27-62-11 | D40442P | 19 | | | TB0211K | A002 | 1 | | 001-099 |
| 3001Y | 20 | HN | AC | | 0-0 | 27-62-11 | D40442P | 19 | | | TB0211K | C005 | 1 | | 115-199 |
| 4501G | 18 | UY | TA | | 17-0 | 32-46-11 | D40442P | 13 | 4G | | TB0211K | A002 | 1 | | 115-199 |
| 4501W | 18 | UY | TA | | 0-0 | 32-46-11 | D40442P | 14 | 4K | | TB0211K | E002 | 1 | | 115-199 |
| 4502G | 18 | UY | TB | | 17-0 | 32-46-11 | D40442P | 1 | 4G | | TB0211K | A001 | 1 | | 115-199 |
| 4502W | 18 | UY | TB | | 0-0 | 32-46-11 | D40442P | 2 | 4K | | TB0211K | C001 | 1 | | 115-199 |
| W4912 | 286N4912 | | | MN LNDG GEAR - WING/TRUCK DISC TO AFT JCTN BOX - RIGHT | | | | | | | | | | | |
| 2001B | 18 | HM | CC | | 19-0 | 32-09-12 | D40434P | 12 | | | TB0212K | G001 | 1 | | 001-099 |
| 2001B | 18 | HM | CC | | 20-0 | 32-09-12 | D40434P | 12 | | | TB0212K | G001 | 1 | | 115-199 |
| 2001R | 18 | HM | CC | | 0-0 | 32-09-12 | D40434P | 11 | | | TB0212K | E001 | 1 | | ALL |
| 2501B | 20 | HQ | AA | | 19-0 | 32-42-11 | D40434P | 9 | | | TB0212K | E003 | 1 | | 001-099 |
| 2501B | 20 | HQ | AA | | 20-0 | 32-42-11 | D40434P | 9 | | | TB0212K | E003 | 1 | | 115-199 |
| 2501R | 20 | HQ | AA | | 0-0 | 32-42-11 | D40434P | 10 | | | TB0212K | G003 | 1 | | ALL |
| 2501Z | | | AA | | 0-0 | 32-42-11 | D40434P | 7 | | | TB0212L | A004 | 1 | | ALL |
| 2502B | 20 | HQ | AB | | 19-0 | 32-42-11 | D40434P | 3 | | | TB0212K | A003 | 1 | | 001-099 |
| 2502B | 20 | HQ | AB | | 20-0 | 32-42-11 | D40434P | 3 | | | TB0212K | A003 | 1 | | 115-199 |
| 2502R | 20 | HQ | AB | | 0-0 | 32-42-11 | D40434P | 5 | | | TB0212K | C003 | 1 | | ALL |
| 2502Z | | | AB | | 0-0 | 32-42-11 | D40434P | 4 | | | TB0212L | E004 | 1 | | ALL |
| 4501G | 18 | UY | TA | | 20-0 | 32-46-11 | D40434P | 2 | 4G | | TB0212K | C001 | 1 | | 115-199 |
| 4501W | 18 | UY | TA | | 0-0 | 32-46-11 | D40434P | 1 | 4K | | TB0212K | A001 | 1 | | 115-199 |
| 4502G | 18 | UY | TB | | 20-0 | 32-46-11 | D40434P | 14 | 4G | | TB0212K | E002 | 1 | | 115-199 |
| 4502W | 18 | UY | TB | | 0-0 | 32-46-11 | D40434P | 13 | 4K | | TB0212K | A002 | 1 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4910

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|--------|------|------|--------|-------|---------|------|--------|-------------|-----|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | | |
| W4920 | 286N4920 | | | | MN LNDG GEAR - DOWN INDICATION PROX SENSORS SYS 1 - RIGHT | | | | | | | | | | | | |
| A-AA | | | | | 5-0 | 32-61-22 | S10057 | | RED | | | D40432P | 1 | | | ALL | |
| A-AB | | | | | 5-0 | 32-61-22 | S10057 | | BLU | | | D40432P | 2 | | | ALL | |
| W4922 | 286N4922 | | | | MN LNDG GEAR - DOWN INDICATION PROX SENSORS SYS 2 - RIGHT | | | | | | | | | | | | |
| A-AA | | | | | 0-0 | 32-61-22 | S10070 | | RED | | | D40440P | 1 | | | ALL | |
| A-AB | | | | | 0-0 | 32-61-22 | S10070 | | BLU | | | D40440P | 2 | | | ALL | |
| W4924 | 286N4924 | | | | MN LNDG GEAR AFT JCTN BOX TO ANTI-SKID SENSORS - RIGHT | | | | | | | | | | | | |
| 2501B | 20 | HQ | AA | | 3-10 | 32-42-11 | D02044 | | 3 | | | TB0212K | E003 | 1 | | ALL | |
| 2501R | 20 | HQ | AA | | 0-0 | 32-42-11 | D02044 | | 1 | | | TB0212K | G003 | 1 | | ALL | |
| 2501Z | | | AA | | 0-0 | 32-42-11 | D02044 | | DED | | | TB0212L | A004 | 1 | | ALL | |
| 2502B | 20 | HQ | AB | | 3-10 | 32-42-11 | D02046 | | 3 | | | TB0212K | A003 | 1 | | ALL | |
| 2502R | 20 | HQ | AB | | 0-0 | 32-42-11 | D02046 | | 1 | | | TB0212K | C003 | 1 | | ALL | |
| 2502Z | | | AB | | 0-0 | 32-42-11 | D02046 | | DED | | | TB0212L | E004 | 1 | | ALL | |
| W4926 | 286N4926 | | | | MN LNDG GEAR AFT JCTN BOX TO SYS 2 TRUCK TILT PROX SENSORS - RIGHT | | | | | | | | | | | | |
| A-AA | | | | | 0-0 | 32-09-12 | S10059 | | BLU | | | TB0212K | G001 | 1 | | ALL | |
| A-AB | | | | | 0-0 | 32-09-12 | S10059 | | RED | | | TB0212K | E001 | 1 | | ALL | |

WIRE LIST

D280N032

91-21-11
Section W4920
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|--|-------|----------|--------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W4930 | 286N4930 | | | MN LNDG GEAR FWD JCTN BOX TO BRAKE TEMP SENSORS - RIGHT | | | | | | | | | | | |
| 4501G | 18 | UY | TA | | 4-0 | 32-46-11 | D02658 | 3 | 4H | | TB0211K | A001 | 1 | | 115-199 |
| 4501W | 18 | UY | TA | | 0-0 | 32-46-11 | D02658 | 1 | 4L | | TB0211K | C001 | 1 | | 115-199 |
| W4932 | 286N4932 | | | MN LNDG GEAR AFT JCTN BOX TO BRAKE TEMP SENSORS - RIGHT | | | | | | | | | | | |
| 4501G | 18 | UY | TA | | 4-0 | 32-46-11 | D02662 | 3 | 4H | | TB0212K | E002 | 1 | | 115-199 |
| 4501W | 18 | UY | TA | | 0-0 | 32-46-11 | D02662 | 1 | 4L | | TB0212K | A002 | 1 | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W4930

Page 1 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|-----|---|----------|--|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | FT-IN | Diagram | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5100 | 286N5100 | | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL | | | | | | | | | | | |
| 0002 | 18 | | 5J | | 10-5 | 26-13-11 | | D01108J | | 3 | | D42282J | | 2 | | ALL |
| 0003 | 18 | | 5J | | 10-5 | 26-13-11 | | D01108J | | 6 | | D42282J | | 5 | | ALL |
| 0005 | 20 | | 5J | | 10-5 | 29-11-11 | | D01108J | | 7 | | D42282J | | 1 | | ALL |
| 0011R | 20 | | FV | | 10-5 | 26-11-11 | | D01108J | | 1 | | D42282J | | 4 | | ALL |
| 0012R | 20 | | FV | | 10-5 | 26-11-11 | | D01108J | | 5 | | D42282J | | 8 | | ALL |
| 0013R | 20 | | FV | | 10-5 | 26-11-11 | | D01108J | | 13 | | D42282J | | 6 | | ALL |
| 0017 | 18 | | 5J | | 2-3 | 76-11-11 | | D01108J | | 9 | | GD02166 | DC.. | N | | ALL |
| 0036 | 20 | | 5J | | 10-3 | 29-22-11 | | D42282J | | 23 | | D06240 | | 5 | | ALL |
| 0037 | 20 | | 5J | | 10-3 | 29-22-11 | | D42282J | | 24 | | D06240 | | 4 | | ALL |
| 0038 | 20 | | 5J | | 10-3 | 29-22-11 | | D42282J | | 25 | | D06240 | | 6 | | ALL |
| 0057 | 20 | | 5J | | 10-5 | SPARE | | D42282J | | 11 | | D01108J | | 16 | | ALL |
| 0058 | 20 | | 5J | | 10-5 | SPARE | | D42282J | | 12 | | D01108J | | 17 | | ALL |
| 0059 | 18 | | 7A | | 3-5 | 26-18-11 | | D42282J | | 14 | | D01950 | = 1 | | | ALL |
| 0061 | 20 | | 5J | | 11-7 | 29-11-11 | | D42282J | | 10 | | D01774 | B | | | ALL |
| 0062 | 20 | | 5J | | 11-7 | 29-11-11 | | D42282J | | 13 | | D01774 | A | | | ALL |
| 0063 | 18 | | 5J | | 3-4 | 29-11-11 | | D01774 | | E | | GD00172 | DC.. | N | | ALL |
| 0066 | 20 | | 5J | | 9-11 | SPARE | | D01104J | | 10 | | D42280J | | 6 | | 001-099 |
| 0067 | 20 | | 5J | | 9-5 | 29-11-12 | | D06240 | | 3 | | D42280J | | 7 | | ALL |
| 0069 | 18 | | 5J | | 4-2 | 29-11-12 | | D06240 | | 2 | | GD02676 | DC.. | N | | ALL |
| 0072 | 20 | | 5J | | 9-7 | 29-11-12 | | D03100 | | 3 | | D42280J | | 8 | | ALL |
| 0073 | 18 | | 5J | | 4-4 | 29-11-12 | | D03100 | | 2 | | GD02676 | DC.. | N | | ALL |
| 0074 | 18 | | 5J | | 2-1 | 71-51-11 | | D01104J | | 1 | | GD02166 | DC.. | N | | ALL |
| 0075 | 18 | | 5J | | 2-3 | 71-51-11 | | D01108J | | 12 | | GD02166 | DC.. | N | | ALL |
| 0079R | 18 | | FV | | 2-3 | 26-11-11 | | D01108J | | 15 | | GD02166 | DC.. | N | | ALL |
| 0080 | 20 | | 5J | | 9-7 | 29-11-12 | | D03100 | | 1 | | D42280J | | 11 | | ALL |
| 0092 | 20 | | 1E | | 0-7 | 73-21-11 | | D01104J | | | AC | D01104J | S/R | | | ALL |
| 0093 | 20 | | 1E | | 0-7 | 75-31-11 | | D01104J | | | AA | D01104J | S/R | | | ALL |
| 0094 | 20 | | 1E | | 0-7 | 77-21-11 | | D01104J | | | AB | D01104J | S/R | | | ALL |
| 0095 | 20 | | 5J | | 9-5 | 29-22-11 | | D42280J | | 10 | | D06240 | | 1 | | ALL |
| 0096 | 20 | | 5J | | 9-11 | SPARE | | D42280J | | 26 | | D01104J | | 23 | | 001-099 |
| 0097 | 20 | | 5J | | 9-11 | SPARE | | D42280J | | 27 | | D01104J | | 24 | | 001-099 |
| 1001 | 18 | | 5N | AP | 10-3 | 73-21-11 | | D01104J | | 34 | | D42282J | | 16 | | 001-099 |
| 1001 | 18 | | 5N | AG | 10-3 | 73-21-11 | | D01104J | | 34 | | D42282J | | 16 | | 115-199 |
| 1001Z | | | | AP | 0-0 | 73-21-11 | | D01104J | | S/R | | D42282J | | S/R | | 001-099 |
| 1001Z | | | | AG | 0-0 | 73-21-11 | | D01104J | | S/R | | D42282J | | S/R | | 115-199 |
| 1002 | 20 | | 5N | AS | 10-1 | 76-11-11 | | D01108J | | 8 | | D42280J | | 1 | | 001-099 |
| 1002 | 20 | | 5N | AH | 10-1 | 76-11-11 | | D01108J | | 8 | | D42280J | | 1 | | 115-199 |
| 1002Z | | | | AS | 0-0 | 76-11-11 | | D01108J | | S/R | | D42280J | | S/R | | 001-099 |
| 1002Z | | | | AH | 0-0 | 76-11-11 | | D01108J | | S/R | | D42280J | | S/R | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W5100

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------|-------------|----|-------|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5100 | 286N5100 | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL (continued) | | | | | | | | | | | |
| 1003 | 20 | 5N | AB | | 9-11 | SPARE | D01104J | 2 | | | D42280J | 19 | | | 001-099 |
| 1003Z | | | AB | | 0-0 | SPARE | D01104J | S/R | | | D42280J | S/R | | | 001-099 |
| 1007 | 18 | 5N | AC | | 29-8 | 28-22-21 | D42280J | 9 | | | D02142 | 6 | | | 001-099 |
| 1007 | 18 | 5N | AN | | 29-8 | 28-22-21 | D42280J | 9 | | | D02142 | 6 | | | 115-199 |
| 1007Z | | | AC | | 0-0 | 28-22-21 | D42280J | S/R | | | GD02319 | ST.. | E | | 001-099 |
| 1007Z | | | AN | | 0-0 | 28-22-21 | D42280J | S/R | | | GD02319 | ST.. | E | | 115-199 |
| 1008 | 20 | 5N | AP | | 30-1 | 28-41-21 | D42280J | 12 | | | SP00043 | | 9 | | 115-199 |
| 1008Z | | | AP | | 0-0 | 28-41-21 | D42280J | S/R | | | SP00043 | REF | | AP | 115-199 |
| 2501B | 20 | 5P | AX | | 9-11 | 73-21-11 | D01104J | 14 | | | D42280J | 5 | | | 001-099 |
| 2501B | 20 | 5P | AA | | 9-11 | 73-21-11 | D01104J | 14 | | | D42280J | 5 | | | 115-199 |
| 2501R | 20 | 5P | AX | | 0-0 | 73-21-11 | D01104J | 13 | | | D42280J | 15 | | | 001-099 |
| 2501R | 20 | 5P | AA | | 0-0 | 73-21-11 | D01104J | 13 | | | D42280J | 15 | | | 115-199 |
| 2501Z | | | AX | | 0-0 | 73-21-11 | D01104J | | | AC | D42280J | | | AD | 001-099 |
| 2501Z | | | AA | | 0-0 | 73-21-11 | D01104J | | | AC | D42280J | | | AD | 115-199 |
| 2502B | 20 | 5P | AU | | 9-11 | 73-21-11 | D01104J | 21 | | | D42280J | 16 | | | 001-099 |
| 2502B | 20 | 5P | AB | | 9-11 | 73-21-11 | D01104J | 21 | | | D42280J | 16 | | | 115-199 |
| 2502R | 20 | 5P | AU | | 0-0 | 73-21-11 | D01104J | 9 | | | D42280J | 17 | | | 001-099 |
| 2502R | 20 | 5P | AB | | 0-0 | 73-21-11 | D01104J | 9 | | | D42280J | 17 | | | 115-199 |
| 2502Z | | | AU | | 0-0 | 73-21-11 | D01104J | | | AC | D42280J | | | AD | 001-099 |
| 2502Z | | | AB | | 0-0 | 73-21-11 | D01104J | | | AC | D42280J | | | AD | 115-199 |
| 2503B | 20 | 5P | AV | | 9-11 | 73-21-11 | D01104J | 12 | | | D42280J | 31 | | | 001-099 |
| 2503B | 20 | 5P | AC | | 9-11 | 73-21-11 | D01104J | 12 | | | D42280J | 31 | | | 115-199 |
| 2503R | 20 | 5P | AV | | 0-0 | 73-21-11 | D01104J | 4 | | | D42280J | 32 | | | 001-099 |
| 2503R | 20 | 5P | AC | | 0-0 | 73-21-11 | D01104J | 4 | | | D42280J | 32 | | | 115-199 |
| 2503Z | | | AV | | 0-0 | 73-21-11 | D01104J | | | AC | D42280J | | | AD | 001-099 |
| 2503Z | | | AC | | 0-0 | 73-21-11 | D01104J | | | AC | D42280J | | | AD | 115-199 |
| 2504B | 18 | 5P | AF | | 10-3 | 75-31-11 | D01104J | 35 | | | D42282J | 15 | | | ALL |
| 2504R | 18 | 5P | AF | | 0-0 | 75-31-11 | D01104J | 36 | | | D42282J | 17 | | | ALL |
| 2504Z | | | AF | | 0-0 | 75-31-11 | D01104J | S/R | | | D42282J | S/R | | | ALL |
| 2505B | 20 | 5P | AK | | 9-11 | SPARE | D01104J | 6 | | | D42280J | 2 | | | 115-199 |
| 2505R | 20 | 5P | AK | | 0-0 | SPARE | D01104J | 31 | | | D42280J | 3 | | | 115-199 |
| 2505Z | | | AK | | 0-0 | SPARE | D01104J | S/R | | | D42280J | S/R | | | 115-199 |
| 2506B | 20 | 5P | AM | | 9-11 | SPARE | D01104J | 8 | | | D42280J | 4 | | | 115-199 |
| 2506R | 20 | 5P | AM | | 0-0 | SPARE | D01104J | 20 | | | D42280J | 6 | | | 115-199 |
| 2506Z | | | AM | | 0-0 | SPARE | D01104J | S/R | | | D42280J | S/R | | | 115-199 |
| 2510B | 20 | 5P | AY | | 9-11 | SPARE | D42280J | 20 | | | D01104J | 15 | | | 001-099 |
| 2510R | 20 | 5P | AY | | 0-0 | SPARE | D42280J | 21 | | | D01104J | 16 | | | 001-099 |
| 2510Z | | | AY | | 0-0 | SPARE | D42280J | 22 | | | D01104J | 17 | | | 001-099 |
| 2511B | 20 | 5P | AZ | | 9-11 | SPARE | D42280J | 23 | | | D01104J | 18 | | | 001-099 |

WIRE LIST

D280N032

91-21-11

Section W5100

Page 2

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5100 | 286N5100 | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL (continued) | | | | | | | | | | | |
| 2511R | 20 | 5P | AZ | | 0-0 | SPARE | D42280J | 24 | | | D01104J | 19 | | | 001-099 |
| 2511Z | | | AZ | | 0-0 | SPARE | D42280J | 25 | | | D01104J | 20 | | | 001-099 |
| 3503B | 20 | 5Q | AT | | 10-5 | 76-11-11 | D01108J | 11 | | | D42282J | 3 | | | 001-099 |
| 3503B | 20 | 5Q | AJ | | 10-5 | 76-11-11 | D01108J | 11 | | | D42282J | 3 | | | 115-199 |
| 3503R | 20 | 5Q | AT | | 0-0 | 76-11-11 | D01108J | 4 | | | D42282J | 7 | | | 001-099 |
| 3503R | 20 | 5Q | AJ | | 0-0 | 76-11-11 | D01108J | 4 | | | D42282J | 7 | | | 115-199 |
| 3503Y | 20 | 5Q | AT | | 0-0 | 76-11-11 | D01108J | 10 | | | D42282J | 9 | | | 001-099 |
| 3503Y | 20 | 5Q | AJ | | 0-0 | 76-11-11 | D01108J | 10 | | | D42282J | 9 | | | 115-199 |
| 3503Z | | | AT | | 0-0 | 76-11-11 | D01108J | S/R | | | D42282J | S/R | | | 001-099 |
| 3503Z | | | AJ | | 0-0 | 76-11-11 | D01108J | S/R | | | D42282J | S/R | | | 115-199 |
| 3504B | 20 | 5Q | AA | | 9-11 | SPARE | D01104J | 6 | | | D42280J | 2 | | | 001-099 |
| 3504R | 20 | 5Q | AA | | 0-0 | SPARE | D01104J | 31 | | | D42280J | 3 | | | 001-099 |
| 3504Y | 20 | 5Q | AA | | 0-0 | SPARE | D01104J | 8 | | | D42280J | 4 | | | 001-099 |
| 3504Z | | | AA | | 0-0 | SPARE | D01104J | S/R | | | D42280J | S/R | | | 001-099 |
| 4501G | 20 | DU | AW | | 9-11 | 75-31-11 | D01104J | 38 | 4B | | D42280J | 33 | | | 001-099 |
| 4501G | 20 | DU | AD | | 9-11 | 75-31-11 | D01104J | 38 | 4B | | D42280J | 33 | | | 115-199 |
| 4501W | 20 | DU | AW | | 0-0 | 75-31-11 | D01104J | 37 | 4D | | D42280J | 34 | | | 001-099 |
| 4501W | 20 | DU | AD | | 0-0 | 75-31-11 | D01104J | 37 | 4D | | D42280J | 34 | | | 115-199 |
| 4501Z | | | AW | | 0-0 | 75-31-11 | D01104J | | | AA | D42280J | S/R | | | 001-099 |
| 4501Z | | | AD | | 0-0 | 75-31-11 | D01104J | | | AA | D42280J | S/R | | | 115-199 |
| 4502G | 20 | DU | AE | | 9-11 | 77-21-11 | D01104J | 28 | 4B | | D42280J | 35 | | | ALL |
| 4502W | 20 | DU | AE | | 0-0 | 77-21-11 | D01104J | 27 | 4D | | D42280J | 36 | | | ALL |
| 4502Z | | | AE | | 0-0 | 77-21-11 | D01104J | | | AB | D42280J | S/R | | | ALL |
| FRAA | | | | | 0-0 | 75-31-11 | D01104J | | | AA | D01104J | 39 | | | 001-099 |
| FRAA | | | | | 0-3 | 75-31-11 | D01104J | | | AA | D01104J | 39 | | | 115-199 |
| FRAB | | | | | 0-0 | 77-21-11 | D01104J | | | AB | D01104J | 32 | | | 001-099 |
| FRAB | | | | | 0-3 | 77-21-11 | D01104J | | | AB | D01104J | 32 | | | 115-199 |
| FRAC | | | | | 0-0 | 73-21-11 | D01104J | | | AC | D01104J | 3 | | | 001-099 |
| FRAC | | | | | 0-3 | 73-21-11 | D01104J | | | AC | D01104J | 3 | | | 115-199 |
| FRAD | | | | | 0-0 | 73-21-11 | D42280J | | | AD | D42280J | 30 | | | 001-099 |
| FRAD | | | | | 0-3 | 73-21-11 | D42280J | | | AD | D42280J | 30 | | | 115-199 |
| FRAP | | | | | 0-6 | 28-41-21 | SP00043 | REF | | AP | GD00997 | ST.. | N | | 115-199 |
| YAAA | | | | | 0-0 | 29-11-11 | GD00073 | ST.. | N | | GD00747 | ST.. | N | | ALL |
| W5102 | 286N5102 | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL | | | | | | | | | | | |
| 0004 | 18 | 7A | | | 6-2 | 26-18-11 | D42276P | 26 | | | D01946 | = 1 | | | ALL |
| 0006 | 18 | 5J | | | 10-2 | 29-32-11 | D42276P | 1 | | | D02152 | 2 | | | ALL |
| 0007 | 18 | 5J | | | 5-2 | 29-32-11 | D02152 | 1 | | | GD02676 | DC.. | N | | ALL |
| 0008 | 20 | 1E | | | 0-7 | 79-34-11 | D01102J | | | AE | D01102J | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W5100

Page 3

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | From | | | To | | | | | | | |
|------------|-------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|------------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5102 | 286N5102 | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL (continued) | | | | | | | | | | | |
| 0009 | 20 | | 1E | | 0-7 | 79-34-11 | D01102J | | | AF | D01102J | S/R | | | ALL |
| 0013 | 18 | | 5J | | 1-5 | 74-31-11 | D01102J | 32 | | | GD00221 | AC.. | N | | ALL |
| 0017 | 20 | | 5J | | 12-4 | 78-36-11 | D42276P | 8 | | | D02900 | 1 | | | ALL |
| 0018 | 20 | | 5J | | 12-4 | 78-36-11 | D42276P | 9 | | | D02900 | 2 | | | 001-002, 115-199 |
| 0018 | 20 | | 5J | | 12-4 | 78-36-11 | D42276P | 9 | | | D02900 | 3 | | | 003-099 |
| 0020 | 20 | | 5J | | 11-3 | 76-11-11 | D42276P | 10 | | | D01102J | 10 | | | ALL |
| 0021 | 20 | | 5J | | 11-3 | 76-11-11 | D42276P | 11 | | | D01102J | 8 | | | ALL |
| 0027 | 18 | | 5J | | 1-5 | 71-51-11 | D01102J | 2 | | | GD00186 | DC.. | N | | ALL |
| 0028 | 18 | | 5J | | 3-10 | 29-32-11 | D02152 | 3 | | | GD01614 | ST.. | N | | ALL |
| 0030 | 18 | | 5J | | 1-5 | 79-34-11 | D01102J | 22 | | | GD00186 | DC.. | N | *1 | ALL |
| 0032 | 18 | | 5J | | 1-5 | 71-51-11 | D01102J | 25 | | | GD00186 | DC.. | N | | ALL |
| 0034 | 18 | | 5J | | 1-5 | 79-34-11 | D01102J | 34 | | | GD00186 | DC.. | N | *2 | ALL |
| 0035 | 20 | | 5J | | 11-3 | SPARE | D42276P | 32 | | | D01102J | 42 | | | 115-199 |
| 0036 | 20 | | 5J | | 12-4 | 78-36-11 | D42276P | 29 | | | D02900 | 2 | | | 003-099 |
| 1001 | 20 | | 5N | T | 11-3 | 76-11-21 | D42276P | 7 | | | D01102J | 3 | | | ALL |
| 1001Z | | | | T | 0-0 | 76-11-21 | D42276P | S/R | | | D01102J | S/R | | | ALL |
| 2501B | 20 | | 5P | AF | 11-6 | 79-34-11 | D42276P | 15 | | | GD00186 | DC.. | N | *1 | ALL |
| 2501R | 20 | | 5P | AF | 0-0 | 79-34-11 | D42276P | 16 | | | D01102J | 9 | | | ALL |
| 2501Z | | | | AF | 0-0 | 79-34-11 | D42276P | S/R | | | D01102J | | | AE | ALL |
| 2502B | 20 | | 5P | AG | 11-6 | 79-34-11 | D42276P | 27 | | | GD00186 | DC.. | N | *2 | ALL |
| 2502R | 20 | | 5P | AG | 0-0 | 79-34-11 | D42276P | 28 | | | D01102J | 33 | | | ALL |
| 2502Z | | | | AG | 0-0 | 79-34-11 | D42276P | S/R | | | D01102J | | | AF | ALL |
| 2503B | 20 | | 5P | AJ | 11-3 | 74-31-11 | D42276P | 5 | | | D01102J | 31 | | | ALL |
| 2503R | 20 | | 5P | AJ | 0-0 | 74-31-11 | D42276P | 6 | | | D01102J | 16 | | | ALL |
| 2503Z | | | | AJ | 0-0 | 74-31-11 | D42276P | S/R | | | D01102J | S/R | | | ALL |
| 2504B | 20 | | 5P | AA | 11-3 | SPARE | D42276P | 32 | | | D01102J | 42 | | | 001-099 |
| 2504R | 20 | | 5P | AA | 0-0 | SPARE | D42276P | 33 | | | D01102J | 40 | | | 001-099 |
| 2504Z | | | | AA | 0-0 | SPARE | D42276P | 35 | | | D01102J | 24 | | | 001-099 |
| 2505B | 20 | | 5P | AL | 11-3 | SPARE | D42276P | 33 | | | D01102J | 40 | | | 115-199 |
| 2505R | 20 | | 5P | AL | 0-0 | SPARE | D42276P | 34 | | | D01102J | 41 | | | 115-199 |
| 2505Z | | | | AL | 0-0 | SPARE | D42276P | 35 | | | D01102J | 24 | | | 115-199 |
| 3502B | 20 | | 5Q | AH | 11-3 | 30-21-11 | D42276P | 2 | | | D01102J | 11 | | | ALL |
| 3502R | 20 | | 5Q | AH | 0-0 | 30-21-11 | D42276P | 3 | | | D01102J | 6 | | | ALL |
| 3502Y | 20 | | 5Q | AH | 0-0 | 30-21-11 | D42276P | 4 | | | D01102J | 7 | | | ALL |
| 3502Z | | | | AH | 0-0 | 30-21-11 | D42276P | S/R | | | D01102J | S/R | | | ALL |
| 3503B | 20 | | 5Q | AB | 11-3 | 73-31-11 | D42276P | 19 | | | D01102J | 19 | | | ALL |
| 3503R | 20 | | 5Q | AB | 0-0 | 73-31-11 | D42276P | 18 | | | D01102J | 18 | | | ALL |
| 3503Y | 20 | | 5Q | AB | 0-0 | 73-31-11 | D42276P | 17 | | | D01102J | 35 | | | ALL |
| 3503Z | | | | AB | 0-0 | 73-31-11 | D42276P | S/R | | | D01102J | S/R | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W5100

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | Diagram | From | | | | To | | | | Effectivity | | |
|------------------------|-------------|----|----|-----|--|----------|---------|---------|------|--------|-------|---------|------|--------|---|-------------|--|--|
| | GA | CO | TY | | FT-IN | Equip | | Term | Type | Splice | Equip | Term | Type | Splice | | | | |
| W5102 | 286N5102 | | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL (continued) | | | | | | | | | | | | | |
| 3504B | 20 | 5Q | AD | | 11-3 | 79-31-11 | | D42276P | 20 | | | D01102J | 20 | | | ALL | | |
| 3504R | 20 | 5Q | AD | | 0-0 | 79-31-11 | | D42276P | 21 | | | D01102J | 36 | | | ALL | | |
| 3504Y | 20 | 5Q | AD | | 0-0 | 79-31-11 | | D42276P | 22 | | | D01102J | 37 | | | ALL | | |
| 3504Z | | | AD | | 0-0 | 79-31-11 | | D42276P | S/R | | | D01102J | S/R | | | ALL | | |
| 3505B | 20 | 5Q | AE | | 11-3 | 79-32-11 | | D42276P | 23 | | | D01102J | 15 | | | ALL | | |
| 3505R | 20 | 5Q | AE | | 0-0 | 79-32-11 | | D42276P | 24 | | | D01102J | 30 | | | ALL | | |
| 3505Y | 20 | 5Q | AE | | 0-0 | 79-32-11 | | D42276P | 25 | | | D01102J | 14 | | | ALL | | |
| 3505Z | | | AE | | 0-0 | 79-32-11 | | D42276P | S/R | | | D01102J | S/R | | | ALL | | |
| 3506B | 20 | 5Q | AK | | 11-3 | SPARE | | D42276P | 12 | | | D01102J | 1 | | | ALL | | |
| 3506R | 20 | 5Q | AK | | 0-0 | SPARE | | D42276P | 13 | | | D01102J | 4 | | | ALL | | |
| 3506Y | 20 | 5Q | AK | | 0-0 | SPARE | | D42276P | 14 | | | D01102J | 5 | | | ALL | | |
| 3506Z | | | AK | | 0-0 | SPARE | | D01102J | S/R | | | D42276P | S/R | | | ALL | | |
| FRAE | | | | | 0-3 | 79-34-11 | | D01102J | | | AE | D01102J | 23 | | | ALL | | |
| FRAF | | | | | 0-3 | 79-34-11 | | D01102J | | | AF | D01102J | 17 | | | ALL | | |
| YAAD | | | | | 0-0 | 29-32-11 | | GD00073 | ST.. | N | | GD00747 | ST.. | N | | ALL | | |
| W5104 | 286N5104 | | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL | | | | | | | | | | | | | |
| 0001 | 18 | 5J | | | 2-2 | 71-51-11 | | D01106J | 7 | | | GD00187 | DC.. | N | | ALL | | |
| 0002 | 20 | 5J | | | 0-7 | 77-31-11 | | D42272J | 7 | | | D42272J | 8 | | | ALL | | |
| 0003 | 20 | 5J | | | 0-7 | 77-31-11 | | D42272J | 18 | | | D42272J | 34 | | | ALL | | |
| 0006 | 18 | 5J | | | 2-2 | 71-51-11 | | D01106J | 19 | | | GD00187 | DC.. | N | | ALL | | |
| 0007 | 18 | 5J | | | 2-2 | 71-51-11 | | D01106J | 18 | | | GD00187 | DC.. | N | | ALL | | |
| 0008 | 20 | 5J | | | 0-7 | 77-31-11 | | D42272J | 21 | | | D42272J | 39 | | | ALL | | |
| 0009 | 18 | 5J | | | 2-2 | 80-11-11 | | D01106J | 9 | | | GD00187 | DC.. | N | | ALL | | |
| 0010 | 20 | 5J | | | 10-11 | SPARE | | D42272J | 5 | | | D01106J | 32 | | | 115-199 | | |
| 0025 | 20 | 1E | | | 0-7 | 77-12-31 | | D01106J | | | AH | D01106J | S/R | | | ALL | | |
| 0026 | 20 | 1E | | | 0-7 | 77-11-11 | | D01106J | | | AF | D01106J | S/R | | | ALL | | |
| 0027 | 20 | 1E | | | 0-7 | 77-11-11 | | D01106J | | | AA | D01106J | S/R | | | 001-099 | | |
| 0027 | 20 | 1E | | | 0-7 | 77-11-11 | | D01106J | | | AG | D01106J | S/R | | | 115-199 | | |
| 0028 | 20 | 5J | | | 10-11 | SPARE | | D42272J | 6 | | | D01106J | 31 | | | 001-099 | | |
| 0029 | 20 | 5J | | | 10-11 | SPARE | | D42272J | 9 | | | D01106J | 33 | | | 001-099 | | |
| 1003 | 18 | 5N | T | | 2-2 | 77-11-11 | | D01106J | 30 | | | GD00221 | AC.. | N | * | ALL | | |
| 1003Z | | | T | | 0-0 | 77-11-11 | | D01106J | S/R | | | GD00221 | AC.. | N | * | ALL | | |
| 1004 | 20 | 5N | U | | 10-11 | 77-11-11 | | D42272J | 3 | | | D01106J | 29 | | | ALL | | |
| 1004Z | | | U | | 0-0 | 77-11-11 | | D42272J | S/R | | | D01106J | S/R | | | ALL | | |
| 2001B | 18 | 5K | AE | | 10-11 | 22-33-11 | | D42272J | 13 | | | D01106J | 26 | | | ALL | | |
| 2001R | 18 | 5K | AE | | 0-0 | 22-33-11 | | D42272J | 14 | | | D01106J | 25 | | | ALL | | |
| 2002B | 18 | 5K | AF | | 10-11 | 22-33-11 | | D42272J | 15 | | | D01106J | 24 | | | ALL | | |
| 2002R | 18 | 5K | AF | | 0-0 | 22-33-11 | | D42272J | 16 | | | D01106J | 23 | | | ALL | | |

WIRE LIST

D280N032

91-21-11

Section W5100

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5104 | 286N5104 | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL (continued) | | | | | | | | | | | |
| 2501B | 20 | 5P | AD | | 10-11 | 77-12-31 | D42272J | 31 | | | D01106J | 12 | | | ALL |
| 2501R | 20 | 5P | AD | | 0-0 | 77-12-31 | D42272J | 32 | | | D01106J | 11 | | | ALL |
| 2501Z | | | AD | | 0-0 | 77-12-31 | D42272J | S/R | | | D01106J | | | AH | ALL |
| 2502B | 20 | 5P | AP | | 10-11 | SPARE | D42272J | 26 | | | D01106J | 20 | | | 001-099 |
| 2502B | 20 | 5P | AN | | 10-11 | SPARE | D42272J | 6 | | | D01106J | 13 | | | 115-199 |
| 2502R | 20 | 5P | AP | | 0-0 | SPARE | D42272J | 25 | | | D01106J | 22 | | | 001-099 |
| 2502R | 20 | 5P | AN | | 0-0 | SPARE | D42272J | 28 | | | D01106J | 20 | | | 115-199 |
| 2502Z | | | AP | | 0-0 | SPARE | D42272J | S/R | | | D01106J | S/R | | | 001-099 |
| 2502Z | | | AN | | 0-0 | SPARE | D42272J | S/R | | | D01106J | S/R | | | 115-199 |
| 2503B | 18 | 5P | AH | | 10-11 | 73-21-12 | D42272J | 10 | | | D01106J | 28 | | | ALL |
| 2503R | 18 | 5P | AH | | 0-0 | 73-21-12 | D42272J | 11 | | | D01106J | 27 | | | ALL |
| 2503Z | | | AH | | 0-0 | 73-21-12 | D42272J | S/R | | | D01106J | S/R | | | ALL |
| 2504B | 20 | 5P | AK | | 10-11 | 75-31-11 | D42272J | 1 | | | D01106J | 6 | | | ALL |
| 2504R | 20 | 5P | AK | | 0-0 | 75-31-11 | D42272J | 4 | | | D01106J | 4 | | | ALL |
| 2504Z | | | AK | | 0-0 | 75-31-11 | D42272J | S/R | | | D01106J | S/R | | | ALL |
| 2505B | 18 | 5P | AJ | | 10-11 | 75-31-11 | D42272J | 2 | | | D01106J | 8 | | | ALL |
| 2505R | 18 | 5P | AJ | | 0-0 | 75-31-11 | D42272J | 12 | | | D01106J | 10 | | | ALL |
| 2505Z | | | AJ | | 0-0 | 75-31-11 | D42272J | S/R | | | D01106J | S/R | | | ALL |
| 2506B | 20 | 5P | AG | | 10-11 | SPARE | D01106J | 32 | | | D42272J | 5 | | | 001-099 |
| 2506B | 18 | 5P | AM | | 10-11 | 73-21-11 | D42272J | 29 | | | D01106J | 17 | | | 115-199 |
| 2506R | 20 | 5P | AG | | 0-0 | SPARE | D01106J | 13 | | | D42272J | 27 | | | 001-099 |
| 2506R | 18 | 5P | AM | | 0-0 | 73-21-11 | D42272J | 9 | | | D01106J | 16 | | | 115-199 |
| 2506Z | | | AG | | 0-0 | SPARE | D01106J | S/R | | | D42272J | S/R | | | 001-099 |
| 2506Z | | | AM | | 0-0 | 73-21-11 | D42272J | S/R | | | D01106J | S/R | | | 115-199 |
| 2507B | 18 | 5P | AW | | 10-11 | 73-21-11 | D42272J | 29 | | | D01106J | 17 | | | 001-099 |
| 2507B | 20 | 5P | AP | | 10-11 | SPARE | D42272J | 25 | | | D01106J | 31 | | | 115-199 |
| 2507R | 18 | 5P | AW | | 0-0 | 73-21-11 | D42272J | 30 | | | D01106J | 16 | | | 001-099 |
| 2507R | 20 | 5P | AP | | 0-0 | SPARE | D42272J | 26 | | | D01106J | 33 | | | 115-199 |
| 2507Z | | | AW | | 0-0 | 73-21-11 | D42272J | S/R | | | D01106J | S/R | | | 001-099 |
| 2507Z | | | AP | | 0-0 | SPARE | D42272J | S/R | | | D01106J | S/R | | | 115-199 |
| 4501R | 20 | RJ | AB | | 11-0 | 77-31-11 | D42272J | 19 | | | D01112J | 3 | | | ALL |
| 4501W | 20 | RJ | AB | | 0-0 | 77-31-11 | D42272J | 35 | | | D01112J | 2 | | | ALL |
| 4501Z | | | AB | | 0-0 | 77-31-11 | D42272J | 20 | | | D01112J | 4 | | | ALL |
| 4502R | 20 | RJ | AC | | 11-0 | 77-31-11 | D42272J | 36 | | | D01112J | 6 | | | ALL |
| 4502W | 20 | RJ | AC | | 0-0 | 77-31-11 | D42272J | 37 | | | D01112J | 5 | | | ALL |
| 4502Z | | | AC | | 0-0 | 77-31-11 | D42272J | 38 | | | D01112J | 7 | | | ALL |
| 5001B | 20 | 5P | AA | | 10-11 | 77-11-11 | D42272J | 40 | | | D01106J | 15 | | | ALL |
| 5001R | 20 | 5P | AA | | 0-0 | 77-11-11 | D42272J | 22 | | | D01106J | 14 | | | ALL |
| 5001Z | | | AA | | 0-0 | 77-11-11 | D42272J | S/R | | | D01106J | | | AF | ALL |

WIRE LIST

D280N032

91-21-11

Section W5100

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|-----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W5104 | 286N5104 | | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL (continued) | | | | | | | | | | | |
| 5002B | 20 | 5P | AR | | 10-11 | 77-11-11 | D42272J | 23 | | | D01106J | 2 | | | 001-099 | |
| 5002B | 20 | 5P | AG | | 10-11 | 77-11-11 | D42272J | 23 | | | D01106J | 2 | | | 115-199 | |
| 5002R | 20 | 5P | AR | | 0-0 | 77-11-11 | D42272J | 24 | | | D01106J | 1 | | | 001-099 | |
| 5002R | 20 | 5P | AG | | 0-0 | 77-11-11 | D42272J | 24 | | | D01106J | 1 | | | 115-199 | |
| 5002Z | | | AR | | 0-0 | 77-11-11 | D42272J | S/R | | | D01106J | | | AA | 001-099 | |
| 5002Z | | | AG | | 0-0 | 77-11-11 | D42272J | S/R | | | D01106J | | | AG | 115-199 | |
| FRAA | | | | | 0-3 | 77-11-11 | D01106J | | | AA | D01106J | 21 | | | 001-099 | |
| FRAF | | | | | 0-3 | 77-11-11 | D01106J | | | AF | D01106J | 5 | | | ALL | |
| FRAG | | | | | 0-3 | 77-11-11 | D01106J | | | AG | D01106J | 21 | | | 115-199 | |
| FRAH | | | | | 0-3 | 77-12-31 | D01106J | | | AH | D01106J | 3 | | | ALL | |
| W5108 | 286N5108 | | | | LEFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL | | | | | | | | | | | |
| 0001 | 18 | 7A | | | 2-1 | 71-51-11 | D01100J | 2 | | | GD00230 | DC.. | N | | ALL | |
| 0005 | 18 | 5J | | | 2-0 | 74-31-11 | D01100J | 33 | | | GD00184 | AC.. | N | | ALL | |
| 0012 | 20 | 5J | | | 11-5 | SPARE | D01100J | 4 | | | D42278P | 16 | | | ALL | |
| 0018R | 20 | FV | | | 11-4 | 26-11-11 | D01110J | 2 | | | D42278P | 25 | | | ALL | |
| 0019R | 20 | FV | | | 11-4 | 26-11-11 | D01110J | 8 | | | D42278P | 33 | | | ALL | |
| 0020R | 20 | FV | | | 11-4 | 26-11-11 | D01110J | 14 | | | D42278P | 27 | | | ALL | |
| 0021 | 18 | 5J | | | 11-4 | 26-13-11 | D01110J | 4 | | | D42278P | 28 | | | ALL | |
| 0022 | 18 | 5J | | | 11-4 | 26-13-11 | D01110J | 5 | | | D42278P | 34 | | | ALL | |
| 0028 | 18 | 5J | | | 2-1 | 80-11-11 | D01100J | 8 | | | GD00230 | DC.. | N | | ALL | |
| 0029 | 18 | 5J | | | 2-1 | 71-51-11 | D01100J | 25 | | | GD00230 | DC.. | N | | ALL | |
| 0030R | 18 | FV | | | 3-6 | 26-11-11 | D01110J | 13 | | | GD00230 | DC.. | N | | ALL | |
| 0031 | 20 | 1E | | | 0-7 | 77-12-11 | D01100J | | | AC | D01100J | S/R | | | ALL | |
| 0032 | 20 | 1E | | | 0-7 | 77-12-21 | D01100J | | | AD | D01100J | S/R | | | ALL | |
| 0033 | 20 | 1E | | | 0-7 | 77-21-11 | D01110J | | | AE | D01110J | S/R | | | ALL | |
| 0037 | 18 | 1E | | | 0-7 | 30-34-21 | D01100J | | | AF | D01100J | S/R | | | ALL | |
| 1001 | 20 | 5N | AL | | 11-11 | 78-34-11 | D42278P | 26 | | | D02902 | 3 | | | ALL | |
| 1001Z | | | AL | | 0-0 | 78-34-11 | D42278P | S/R | | | GD00747 | ST.. | N | * | ALL | |
| 1002 | 18 | 5N | AM | | 5-5 | 78-34-11 | D02902 | 1 | | | GD00172 | DC.. | N | * | ALL | |
| 1002Z | | | AM | | 0-0 | 78-34-11 | GD00747 | ST.. | N | * | GD00172 | DC.. | N | * | ALL | |
| 1004 | 20 | 2E | T | | 11-5 | 74-31-11 | D01100J | 22 | | | D42278P | 15 | | | ALL | |
| 1004Z | | | T | | 0-0 | 74-31-11 | D01100J | S/R | | | D42278P | S/R | | | ALL | |
| 2501B | 20 | 5P | AA | | 11-5 | 77-12-11 | D01100J | 37 | | | D42278P | 5 | | | ALL | |
| 2501R | 20 | 5P | AA | | 0-0 | 77-12-11 | D01100J | 36 | | | D42278P | 4 | | | ALL | |
| 2501Z | | | AA | | 0-0 | 77-12-11 | D01100J | | | AC | D42278P | S/R | | | ALL | |
| 2502B | 20 | 5P | AB | | 11-5 | 77-12-21 | D01100J | 39 | | | D42278P | 8 | | | ALL | |
| 2502R | 20 | 5P | AB | | 0-0 | 77-12-21 | D01100J | 38 | | | D42278P | 7 | | | ALL | |
| 2502Z | | | AB | | 0-0 | 77-12-21 | D01100J | | | AD | D42278P | S/R | | | ALL | |

WIRE LIST

D280N032

91-21-11
Section W5100
Page 7
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5108 | 286N5108 | | | REFT ENGINE STRUT DISC TO LEFT ENGINE FIREWALL (continued) | | | | | | | | | | | |
| 2503B | 20 | 5P | AF | | 11-5 | 74-31-11 | D01100J | 34 | | | D42278P | 2 | | | ALL |
| 2503R | 20 | 5P | AF | | 0-0 | 74-31-11 | D01100J | 17 | | | D42278P | 3 | | | ALL |
| 2503Z | | | AF | | 0-0 | 74-31-11 | D01100J | S/R | | | D42278P | S/R | | | ALL |
| 2504B | 20 | 5P | AG | | 11-5 | SPARE | D01100J | 10 | | | D42278P | 17 | | | ALL |
| 2504R | 20 | 5P | AG | | 0-0 | SPARE | D01100J | 11 | | | D42278P | 18 | | | ALL |
| 2504Z | | | AG | | 0-0 | SPARE | D01100J | S/R | | | D42278P | S/R | | | ALL |
| 2505B | 20 | 5P | AH | | 11-4 | SPARE | D01110J | 9 | | | D42278P | 30 | | | ALL |
| 2505R | 20 | 5P | AH | | 0-0 | SPARE | D01110J | 10 | | | D42278P | 31 | | | ALL |
| 2505Z | | | AH | | 0-0 | SPARE | D01110J | S/R | | | D42278P | S/R | | | ALL |
| 2506B | 18 | 5P | AJ | | 11-5 | 30-34-21 | D01100J | 28 | | | D42278P | 35 | | | ALL |
| 2506R | 18 | 5P | AJ | | 0-0 | 30-34-21 | D01100J | 29 | | | D42278P | 36 | | | ALL |
| 2506Z | | | AJ | | 0-0 | 30-34-21 | D01100J | | | AF | D42278P | S/R | | | ALL |
| 3501B | 20 | 5Q | AE | | 11-5 | 80-11-11 | D01100J | 32 | | | D42278P | 12 | | | ALL |
| 3501R | 20 | 5Q | AE | | 0-0 | 80-11-11 | D01100J | 7 | | | D42278P | 13 | | | ALL |
| 3501Y | 20 | 5Q | AE | | 0-0 | 80-11-11 | D01100J | 9 | | | D42278P | 14 | | | ALL |
| 3501Z | | | AE | | 0-0 | 80-11-11 | D42278P | S/R | | | D01100J | S/R | | | ALL |
| 4251B | 20 | 5R | AD | | 11-5 | 79-35-11 | D01100J | 6 | | | D42278P | 11 | | | ALL |
| 4251G | 20 | 5R | AD | | 0-0 | 79-33-11 | D01100J | 16 | | | D42278P | 10 | | | ALL |
| 4251R | 20 | 5R | AD | | 0-0 | 73-33-11 | D01100J | 5 | | | D42278P | 1 | | | ALL |
| 4251Y | 20 | 5R | AD | | 0-0 | 73-34-11 | D01100J | 1 | | | D42278P | 21 | | | ALL |
| 4251Z | | | AD | | 0-0 | 79-35-11 | D42278P | S/R | | | D01100J | S/R | | | ALL |
| 4501G | 20 | DU | AC | | 11-4 | 77-21-11 | D01110J | 6 | 4B | | D42278P | 22 | | | ALL |
| 4501W | 20 | DU | AC | | 0-0 | 77-21-11 | D01110J | 7 | 4D | | D42278P | 23 | | | ALL |
| 4501Z | | | AC | | 0-0 | 77-21-11 | D01110J | | | AE | D42278P | S/R | | | ALL |
| FRAC | | | | | 0-3 | 77-12-11 | D01100J | | | AC | D01100J | 26 | | | ALL |
| FRAD | | | | | 0-3 | 77-12-21 | D01100J | | | AD | D01100J | 21 | | | ALL |
| FRAE | | | | | 0-3 | 77-21-11 | D01110J | | | AE | D01110J | 1 | | | ALL |
| FRAF | | | | | 0-0 | 30-34-21 | D01100J | | | AF | D01100J | 27 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W5100

Page 8 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5114 | 286N5114 | | | L. W/B DISC TO L. ENG F/W - L. ENG/GEN CONTROL | | | | | | | | | | | |
| 0001 | 20 | | 5J | | 12-0 | 24-11-11 | D40024P | | 8 | | D01114J | | 8 | | ALL |
| 0002 | 16 | | 2A | | 12-0 | 24-11-11 | D40024P | | 4 | | D01114J | | 4 | | ALL |
| 0003 | 16 | | 2A | | 2-0 | 24-11-11 | D01114J | | 21 | | GD00248 | DC.. | N | | ALL |
| 0004 | 18 | | 5J | | 2-0 | 24-11-11 | D01114J | | 20 | | GD00248 | DC.. | N | | ALL |
| 0006 | 20 | | 5J | | 12-0 | SPARE | D40024P | | 25 | | D01114J | | 25 | | ALL |
| 0007 | 20 | | 5J | | 12-0 | SPARE | D40024P | | 26 | | D01114J | | 26 | | ALL |
| 2001B | 20 | | 5K | AD | 12-0 | 24-11-11 | D40024P | | 19 | | D01114J | | 19 | | ALL |
| 2001R | 20 | | 5K | AD | 0-0 | 24-11-11 | D40024P | | 18 | | D01114J | | 18 | | ALL |
| 2002B | 20 | | 5K | AE | 12-0 | 24-11-11 | D40024P | | 7 | | D01114J | | 7 | | ALL |
| 2002R | 20 | | 5K | AE | 0-0 | 24-11-11 | D40024P | | 6 | | D01114J | | 6 | | ALL |
| 2003B | 20 | | 5K | AG | 12-0 | SPARE | D40024P | | 22 | | D01114J | | 22 | | ALL |
| 2003R | 20 | | 5K | AG | 0-0 | SPARE | D40024P | | 23 | | D01114J | | 23 | | ALL |
| 2501B | 20 | | 5P | AB | 12-0 | 24-21-11 | D40024P | | 10 | | D01114J | | 10 | | ALL |
| 2501R | 20 | | 5P | AB | 0-0 | 24-21-11 | D40024P | | 9 | | D01114J | | 9 | | ALL |
| 2501Z | | | | AB | 0-0 | 24-21-11 | D40024P | | 11 | | D01114J | | 11 | | ALL |
| 2502B | 20 | | 5P | AF | 12-0 | 24-11-11 | D40024P | | 2 | | D01114J | | 2 | | ALL |
| 2502R | 20 | | 5P | AF | 0-0 | 24-11-11 | D40024P | | 1 | | D01114J | | 1 | | ALL |
| 2502Z | | | | AF | 0-0 | 24-11-11 | D40024P | | 5 | | D01114J | | 5 | | ALL |
| 3001B | 18 | | 5L | AA | 12-0 | 24-21-11 | D40024P | | 16 | | D01114J | | 16 | | ALL |
| 3001R | 18 | | 5L | AA | 0-0 | 24-21-11 | D40024P | | 15 | | D01114J | | 15 | | ALL |
| 3001Y | 18 | | 5L | AA | 0-0 | 24-21-11 | D40024P | | 17 | | D01114J | | 17 | | ALL |
| 4001B | 20 | | 5M | AC | 12-0 | 24-21-11 | D40024P | | 13 | | D01114J | | 13 | | ALL |
| 4001G | 20 | | 5M | AC | 0-0 | 24-21-11 | D40024P | | 3 | | D01114J | | 3 | | ALL |
| 4001R | 20 | | 5M | AC | 0-0 | 24-21-11 | D40024P | | 12 | | D01114J | | 12 | | ALL |
| 4001Y | 20 | | 5M | AC | 0-0 | 24-21-11 | D40024P | | 14 | | D01114J | | 14 | | ALL |

WIRE LIST

D280N032

91-21-11
Section W5110
Page 1 End
May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | Diagram | From | | | | To | | | | | | |
|------------|-------------|----|-------|-------------|--|----------|---------|-------|------|------|---------|-------|------|------|--------|-------------|
| | Wire No. | GA | CO TY | | | Fam | FT-IN | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5200 | 286N5200 | | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL | | | | | | | | | | | |
| 0028 | 18 | 5J | | | 2-3 | 76-11-12 | D01208J | | 9 | | GD02167 | DC.. | N | | ALL | |
| 0038 | 18 | 7A | | | 3-2 | 26-18-21 | D42292J | | 26 | | D01990 | =1 | | | ALL | |
| 0040R | 20 | FV | | | 12-10 | 26-11-21 | D42294J | | 4 | | D01208J | 1 | | | ALL | |
| 0041R | 20 | FV | | | 12-10 | 26-11-21 | D42294J | | 19 | | D01208J | 5 | | | ALL | |
| 0042R | 20 | FV | | | 12-10 | 26-11-21 | D42294J | | 6 | | D01208J | 13 | | | ALL | |
| 0043 | 20 | 5J | | | 12-1 | 29-11-21 | D42292J | | 4 | | D01846 | A | | | ALL | |
| 0044 | 20 | 5J | | | 12-1 | 29-11-21 | D42292J | | 5 | | D01846 | B | | | ALL | |
| 0046 | 18 | 5J | | | 3-3 | 29-11-21 | D01846 | | E | | GD00190 | DC.. | N | | ALL | |
| 0047 | 20 | 5J | | | 12-10 | 29-11-21 | D42294J | | 7 | | D01208J | 7 | | | ALL | |
| 0052 | 18 | 5J | | | 12-10 | 26-13-21 | D42294J | | 8 | | D01208J | 3 | | | ALL | |
| 0053 | 18 | 5J | | | 12-10 | 26-13-21 | D42294J | | 12 | | D01208J | 6 | | | ALL | |
| 0062 | 20 | 5J | | | 12-9 | SPARE | D42292J | | 6 | | D01208J | 16 | | | ALL | |
| 0064 | 20 | 5J | | | 12-9 | SPARE | D42292J | | 7 | | D01208J | 17 | | | ALL | |
| 0068 | 20 | 5J | | | 10-7 | 29-11-22 | D42292J | | 8 | | D06242 | 3 | | | ALL | |
| 0070 | 18 | 5J | | | 4-2 | 29-11-22 | D06242 | | 2 | | GD00222 | DC.. | N | | ALL | |
| 0073 | 20 | 5J | | | 10-10 | 29-11-22 | D03064 | | 3 | | D42292J | 9 | | | ALL | |
| 0074 | 18 | 5J | | | 4-5 | 29-11-22 | D03064 | | 2 | | GD00222 | DC.. | N | | ALL | |
| 0077 | 18 | 5J | | | 2-3 | 71-51-11 | D01208J | | 12 | | GD02167 | DC.. | N | | ALL | |
| 0078 | 18 | 5J | | | 3-0 | 71-51-11 | D01204J | | 1 | | GD02167 | DC.. | N | | ALL | |
| 0082R | 18 | FV | | | 2-3 | 26-11-21 | D01208J | | 15 | | GD02167 | DC.. | N | | ALL | |
| 0083 | 20 | 5J | | | 10-10 | 29-11-22 | D03064 | | 1 | | D42292J | 12 | | | ALL | |
| 0092 | 20 | 1E | | | 0-7 | 73-21-21 | D01204J | | | AE | D01204J | S/R | | | ALL | |
| 0093 | 20 | 1E | | | 0-7 | 75-31-11 | D01204J | | | AF | D01204J | S/R | | | ALL | |
| 0094 | 20 | 1E | | | 0-7 | 77-21-11 | D01204J | | | AG | D01204J | S/R | | | ALL | |
| 1003 | 18 | 5N | T | | 12-9 | 73-21-21 | D01204J | | 34 | | D42294J | 9 | | | ALL | |
| 1003Z | | | T | | 0-0 | 73-21-21 | D01204J | | S/R | | D42294J | S/R | | | ALL | |
| 1007 | 18 | 5N | AK | | 30-9 | 28-22-21 | D42292J | | 11 | | D02022 | 6 | | | ALL | |
| 1007Z | | | AK | | 0-0 | 28-22-21 | D42292J | | S/R | | GD02419 | ST.. | N | | ALL | |
| 2501B | 20 | 5P | AA | | 12-8 | 73-21-21 | D01204J | | 14 | | D42292J | 14 | | | ALL | |
| 2501R | 20 | 5P | AA | | 0-0 | 73-21-21 | D01204J | | 13 | | D42292J | 13 | | | ALL | |
| 2501Z | | | AA | | 0-0 | 73-21-21 | D01204J | | | AE | D42292J | | | AD | ALL | |
| 2502B | 20 | 5P | AB | | 12-8 | 73-21-21 | D01204J | | 21 | | D42292J | 28 | | | ALL | |
| 2502R | 20 | 5P | AB | | 0-0 | 73-21-21 | D01204J | | 9 | | D42292J | 29 | | | ALL | |
| 2502Z | | | AB | | 0-0 | 73-21-21 | D01204J | | | AE | D42292J | | | AD | ALL | |
| 2503B | 20 | 5P | AC | | 12-8 | 73-21-21 | D01204J | | 12 | | D42292J | 15 | | | ALL | |
| 2503R | 20 | 5P | AC | | 0-0 | 73-21-21 | D01204J | | 4 | | D42292J | 30 | | | ALL | |
| 2503Z | | | AC | | 0-0 | 73-21-21 | D01204J | | | AE | D42292J | | | AD | ALL | |
| 2504B | 18 | 5P | AG | | 12-9 | 75-31-11 | D01204J | | 35 | | D42294J | 11 | | | ALL | |
| 2504R | 18 | 5P | AG | | 0-0 | 75-31-11 | D01204J | | 36 | | D42294J | 17 | | | ALL | |

WIRE LIST

D280N032

91-21-11

Section W5200

Page 1

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Fam | Description | | From | | | | To | | | | Effectivity | |
|------------------------|-------------|----|----|--|-------------|----------|---------|------|------|--------|---------|------|------|--------|------------------|--|
| | GA | CO | TY | | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | | |
| W5200 | 286N5200 | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL (continued) | | | | | | | | | | | | |
| 2504Z | | | | AG | 0-0 | 75-31-11 | D01204J | S/R | | | D42294J | S/R | | | ALL | |
| 2505B | 20 | 5P | | AH | 12-9 | SPARE | D42294J | 1 | | | D01204J | 6 | | | ALL | |
| 2505R | 20 | 5P | | AH | 0-0 | SPARE | D42294J | 2 | | | D01204J | 31 | | | ALL | |
| 2505Z | | | | AH | 0-0 | SPARE | D42294J | S/R | | | D01204J | S/R | | | ALL | |
| 2506B | 20 | 5P | | AJ | 12-9 | SPARE | D42294J | 3 | | | D01204J | 8 | | | ALL | |
| 2506R | 20 | 5P | | AJ | 0-0 | SPARE | D42294J | 5 | | | D01204J | 20 | | | ALL | |
| 2506Z | | | | AJ | 0-0 | SPARE | D42294J | S/R | | | D01204J | S/R | | | ALL | |
| 4252B | 20 | 5R | | AF | 12-9 | 76-11-12 | D01208J | 10 | | | D42292J | 19 | | | ALL | |
| 4252G | 20 | 5R | | AF | 0-0 | 76-11-12 | D01208J | 8 | | | D42292J | 1 | | | ALL | |
| 4252R | 20 | 5R | | AF | 0-0 | 76-11-12 | D01208J | 11 | | | D42292J | 2 | | | ALL | |
| 4252Y | 20 | 5R | | AF | 0-0 | 76-11-12 | D01208J | 4 | | | D42292J | 3 | | | ALL | |
| 4252Z | | | | AF | 0-0 | 76-11-12 | D01208J | S/R | | | D42292J | S/R | | | ALL | |
| 4501G | 20 | DU | | AD | 12-8 | 75-31-11 | D01204J | 38 | 4B | | D42292J | 17 | | | ALL | |
| 4501W | 20 | DU | | AD | 0-0 | 75-31-11 | D01204J | 37 | 4D | | D42292J | 16 | | | ALL | |
| 4501Z | | | | AD | 0-0 | 75-31-11 | D01204J | | | AF | D42292J | S/R | | | ALL | |
| 4502G | 20 | DU | | AE | 12-8 | 77-21-11 | D01204J | 28 | 4B | | D42292J | 33 | | | ALL | |
| 4502W | 20 | DU | | AE | 0-0 | 77-21-11 | D01204J | 27 | 4D | | D42292J | 34 | | | ALL | |
| 4502Z | | | | AE | 0-0 | 77-21-11 | D01204J | | | AG | D42292J | S/R | | | ALL | |
| FRAD | | | | | 0-0 | 73-21-21 | D42292J | | | AD | D42292J | 31 | | | ALL | |
| FRAE | | | | | 0-3 | 73-21-21 | D01204J | | | AE | D01204J | 3 | | | ALL | |
| FRAF | | | | | 0-3 | 75-31-11 | D01204J | | | AF | D01204J | 39 | | | ALL | |
| FRAG | | | | | 0-3 | 77-21-11 | D01204J | | | AG | D01204J | 32 | | | ALL | |
| YAAA | | | | | 0-0 | 29-11-21 | GD00072 | ST.. | N | | GD00783 | ST.. | N | | ALL | |
| W5202 | 286N5202 | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL | | | | | | | | | | | | |
| 0004 | 18 | 7A | | | 3-6 | 26-18-21 | D42288P | 8 | | | D01986 | =1 | | | ALL | |
| 0006 | 18 | 5J | | | 10-5 | 29-32-21 | D42288P | 10 | | | D02200 | 2 | | | ALL | |
| 0007 | 18 | 1E | | | 5-1 | 29-32-21 | D02200 | 1 | | | GD00222 | DC.. | N | | ALL | |
| 0008 | 20 | 1E | | | 0-7 | 79-34-11 | D01202J | | | AE | D01202J | S/R | | | ALL | |
| 0009 | 20 | 1E | | | 0-7 | 79-34-11 | D01202J | | | AF | D01202J | S/R | | | ALL | |
| 0013 | 18 | 5J | | | 1-3 | 74-31-21 | D01202J | 32 | | | GD00224 | AC.. | N | | ALL | |
| 0017 | 20 | 5J | | | 12-3 | 78-36-21 | D42288P | 34 | | | D02830 | 1 | | | ALL | |
| 0018 | 20 | 5J | | | 12-3 | 78-36-21 | D42288P | 35 | | | D02830 | 2 | | | 001-002, 115-199 | |
| 0018 | 20 | 5J | | | 12-3 | 78-36-21 | D42288P | 35 | | | D02830 | 3 | | | 003-099 | |
| 0020 | 20 | 5J | | | 11-9 | 76-11-12 | D42288P | 36 | | | D01202J | 10 | | | ALL | |
| 0021 | 20 | 5J | | | 11-9 | 76-11-12 | D42288P | 37 | | | D01202J | 8 | | | ALL | |
| 0027 | 18 | 5J | | | 1-5 | 71-51-11 | D01202J | 2 | | | GD00194 | DC.. | N | | ALL | |
| 0028 | 18 | 5J | | | 3-10 | 29-32-21 | D02200 | 3 | | | GD01615 | ST.. | N | | ALL | |
| 0031 | 18 | 5J | | | 1-5 | 79-34-11 | D01202J | 22 | | | GD00194 | DC.. | N | *1 | ALL | |

WIRE LIST

D280N032

91-21-11
Section W5200
Page 2
May 17/2006



WIRE LIST
D280N032

BOEING PROPRIETARY - Copyright © Unpublished Work - See title page for details



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5202 | 286N5202 | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL (continued) | | | | | | | | | | | |
| 3506Y | 20 | 5Q | AK | | 0-0 | SPARE | D42288P | 42 | | | D01202J | 5 | | | ALL |
| 3506Z | | | AK | | 0-0 | SPARE | D42288P | S/R | | | D01202J | S/R | | | ALL |
| FRAE | | | | | 0-3 | 79-34-11 | D01202J | | | AE | D01202J | 23 | | | ALL |
| FRAD | | | | | 0-0 | 79-34-11 | D01202J | | | AF | D01202J | 17 | | | ALL |
| YAAD | | | | | 0-0 | 29-32-21 | GD00072 | ST.. | N | | GD00783 | ST.. | N | | ALL |
| W5204 | 286N5204 | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL | | | | | | | | | | | |
| 0005 | 18 | 5J | | | 2-2 | 71-51-11 | D01206J | 7 | | | GD00195 | DC.. | N | | ALL |
| 0006 | 18 | 5J | | | 2-2 | 71-51-11 | D01206J | 19 | | | GD00195 | DC.. | N | | ALL |
| 0007 | 18 | 5J | | | 2-2 | 71-51-11 | D01206J | 18 | | | GD00195 | DC.. | N | | ALL |
| 0009 | 18 | 5J | | | 2-2 | 80-11-21 | D01206J | 9 | | | GD00195 | DC.. | N | | ALL |
| 0010 | 20 | 5J | | | 11-10 | SPARE | D42284J | 15 | | | D01206J | 32 | | | 115-199 |
| 0025 | 20 | 1E | | | 0-7 | 77-12-31 | D01206J | | | AH | D01206J | S/R | | | ALL |
| 0026 | 20 | 1E | | | 0-7 | 77-11-11 | D01206J | | | AF | D01206J | S/R | | | ALL |
| 0027 | 20 | 1E | | | 0-7 | 77-11-11 | D01206J | | | AA | D01206J | S/R | | | 001-099 |
| 0027 | 20 | 1E | | | 0-7 | 77-11-11 | D01206J | | | AG | D01206J | S/R | | | 115-199 |
| 0028 | 20 | 5J | | | 0-7 | 77-31-11 | D42284J | 26 | | | D42284J | 11 | | | ALL |
| 0029 | 20 | 5J | | | 0-7 | 77-31-11 | D42284J | 10 | | | D42284J | 9 | | | ALL |
| 0030 | 20 | 5J | | | 0-7 | 77-31-11 | D42284J | 22 | | | D42284J | 39 | | | ALL |
| 1003 | 18 | 5N | T | | 1-11 | 77-11-11 | D01206J | 30 | | | GD00224 | AC.. | N | * | ALL |
| 1003Z | | | T | | 0-0 | 77-11-11 | D01206J | S/R | | | GD00224 | AC.. | N | * | ALL |
| 1004 | 20 | 5N | U | | 11-10 | 77-11-11 | D42284J | 3 | | | D01206J | 29 | | | ALL |
| 1004Z | | | U | | 0-0 | 77-11-11 | D42284J | S/R | | | D01206J | S/R | | | ALL |
| 2001B | 18 | 5K | AE | | 11-10 | 22-33-11 | D42284J | 14 | | | D01206J | 26 | | | ALL |
| 2001R | 18 | 5K | AE | | 0-0 | 22-33-11 | D42284J | 16 | | | D01206J | 25 | | | ALL |
| 2002B | 18 | 5K | AF | | 11-10 | 22-33-11 | D42284J | 35 | | | D01206J | 24 | | | ALL |
| 2002R | 18 | 5K | AF | | 0-0 | 22-33-11 | D42284J | 6 | | | D01206J | 23 | | | ALL |
| 2501B | 20 | 5P | AD | | 11-10 | 77-12-31 | D42284J | 30 | | | D01206J | 12 | | | ALL |
| 2501R | 20 | 5P | AD | | 0-0 | 77-12-31 | D42284J | 29 | | | D01206J | 11 | | | ALL |
| 2501Z | | | AD | | 0-0 | 77-12-31 | D42284J | S/R | | | D01206J | | | AH | ALL |
| 2502B | 20 | 5P | AN | | 11-10 | SPARE | D42284J | 12 | | | D01206J | 13 | | | 115-199 |
| 2502R | 20 | 5P | AN | | 0-0 | SPARE | D42284J | 18 | | | D01206J | 20 | | | 115-199 |
| 2502Z | | | AN | | 0-0 | SPARE | D42284J | S/R | | | D01206J | S/R | | | 115-199 |
| 2503B | 18 | 5P | AP | | 11-10 | 73-21-22 | D42284J | 8 | | | D01206J | 28 | | | 001-099 |
| 2503B | 18 | 5P | AH | | 11-10 | 73-21-22 | D42284J | 8 | | | D01206J | 28 | | | 115-199 |
| 2503R | 18 | 5P | AP | | 0-0 | 73-21-22 | D42284J | 7 | | | D01206J | 27 | | | 001-099 |
| 2503R | 18 | 5P | AH | | 0-0 | 73-21-22 | D42284J | 7 | | | D01206J | 27 | | | 115-199 |
| 2503Z | | | AP | | 0-0 | 73-21-22 | D42284J | S/R | | | D01206J | S/R | | | 001-099 |
| 2503Z | | | AH | | 0-0 | 73-21-22 | D42284J | S/R | | | D01206J | S/R | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W5200

Page 4

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description Fam | Diagram | From | | | | To | | | | Effectivity |
|------------------------|-------------|----|----|--|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | | | Equip | Term | Type | Splice | Equip | Term | Type | Splice | |
| W5204 | 286N5204 | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL (continued) | | | | | | | | | | |
| 2504B | 20 | 5P | AK | 11-10 | 75-31-11 | D42284J | 1 | | | D01206J | 6 | | | ALL |
| 2504R | 20 | 5P | AK | 0-0 | 75-31-11 | D42284J | 13 | | | D01206J | 4 | | | ALL |
| 2504Z | | | AK | 0-0 | 75-31-11 | D42284J | S/R | | | D01206J | S/R | | | ALL |
| 2505B | 18 | 5P | AJ | 11-10 | 75-31-11 | D42284J | 31 | | | D01206J | 8 | | | ALL |
| 2505R | 18 | 5P | AJ | 0-0 | 75-31-11 | D42284J | 33 | | | D01206J | 10 | | | ALL |
| 2505Z | | | AJ | 0-0 | 75-31-11 | D42284J | S/R | | | D01206J | S/R | | | ALL |
| 2506B | 18 | 5P | AM | 11-10 | 73-21-21 | D42284J | 2 | | | D01206J | 17 | | | 115-199 |
| 2506R | 18 | 5P | AM | 0-0 | 73-21-21 | D42284J | 34 | | | D01206J | 16 | | | 115-199 |
| 2506Z | | | AM | 0-0 | 73-21-21 | D42284J | S/R | | | D01206J | S/R | | | 115-199 |
| 2507B | 18 | 5P | AR | 11-10 | 73-21-21 | D42284J | 2 | | | D01206J | 17 | | | 001-099 |
| 2507B | 20 | 5P | AP | 11-10 | SPARE | D42284J | 19 | | | D01206J | 31 | | | 115-199 |
| 2507R | 18 | 5P | AR | 0-0 | 73-21-21 | D42284J | 34 | | | D01206J | 16 | | | 001-099 |
| 2507R | 20 | 5P | AP | 0-0 | SPARE | D42284J | 20 | | | D01206J | 33 | | | 115-199 |
| 2507Z | | | AR | 0-0 | 73-21-21 | D42284J | S/R | | | D01206J | S/R | | | 001-099 |
| 2507Z | | | AP | 0-0 | SPARE | D42284J | S/R | | | D01206J | S/R | | | 115-199 |
| 2508B | 20 | 5P | AY | 11-10 | SPARE | D01206J | 31 | | | D42284J | 17 | | | 001-099 |
| 2508R | 20 | 5P | AY | 0-0 | SPARE | D01206J | 32 | | | D42284J | 18 | | | 001-099 |
| 2508Z | | | AY | 0-0 | SPARE | D01206J | S/R | | | D42284J | S/R | | | 001-099 |
| 2509B | 20 | 5P | AZ | 11-10 | SPARE | D01206J | 33 | | | D42284J | 19 | | | 001-099 |
| 2509R | 20 | 5P | AZ | 0-0 | SPARE | D01206J | 34 | | | D42284J | 20 | | | 001-099 |
| 2509Z | | | AZ | 0-0 | SPARE | D01206J | S/R | | | D42284J | S/R | | | 001-099 |
| 4501R | 20 | RJ | AB | 11-11 | 77-31-11 | D42284J | 40 | | | D01212J | 3 | | | ALL |
| 4501W | 20 | RJ | AB | 0-0 | 77-31-11 | D42284J | 25 | | | D01212J | 2 | | | ALL |
| 4501Z | | | AB | 0-0 | 77-31-11 | D42284J | 23 | | | D01212J | 4 | | | ALL |
| 4502R | 20 | RJ | AC | 11-11 | 77-31-11 | D42284J | 42 | | | D01212J | 6 | | | ALL |
| 4502W | 20 | RJ | AC | 0-0 | 77-31-11 | D42284J | 41 | | | D01212J | 5 | | | ALL |
| 4502Z | | | AC | 0-0 | 77-31-11 | D42284J | 24 | | | D01212J | 7 | | | ALL |
| 5001B | 20 | 5P | AA | 11-10 | 77-11-11 | D42284J | 4 | | | D01206J | 15 | | | ALL |
| 5001R | 20 | 5P | AA | 0-0 | 77-11-11 | D42284J | 5 | | | D01206J | 14 | | | ALL |
| 5001Z | | | AA | 0-0 | 77-11-11 | D42284J | S/R | | | D01206J | | | AF | ALL |
| 5002B | 20 | 5P | AS | 11-10 | 77-11-11 | D42284J | 37 | | | D01206J | 2 | | | 001-099 |
| 5002B | 20 | 5P | AG | 11-10 | 77-11-11 | D42284J | 37 | | | D01206J | 2 | | | 115-199 |
| 5002R | 20 | 5P | AS | 0-0 | 77-11-11 | D42284J | 36 | | | D01206J | 1 | | | 001-099 |
| 5002R | 20 | 5P | AG | 0-0 | 77-11-11 | D42284J | 36 | | | D01206J | 1 | | | 115-199 |
| 5002Z | | | AS | 0-0 | 77-11-11 | D42284J | S/R | | | D01206J | | | AA | 001-099 |
| 5002Z | | | AG | 0-0 | 77-11-11 | D42284J | S/R | | | D01206J | | | AG | 115-199 |
| FRAA | | | | 0-3 | 77-11-11 | D01206J | | | AA | D01206J | 21 | | | 001-099 |
| FRAF | | | | 0-3 | 77-11-11 | D01206J | | | AF | D01206J | 5 | | | ALL |
| FRAG | | | | 0-3 | 77-11-11 | D01206J | | | AG | D01206J | 21 | | | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W5200

Page 5

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. | Part Number | | | Description | | | From | | | | To | | | | |
|--------------|-----------------|----|----|-------------|-------|---|---------|------|------|--------|---------|------|------|--------|-------------|
| Wire No. | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5204 | 286N5204 | | | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL (continued) | | | | | | | | | |
| FRAH | | | | | 0-3 | 77-12-31 | D01206J | | AH | | D01206J | 3 | | | ALL |
| W5208 | 286N5208 | | | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL | | | | | | | | | |
| 0001 | 18 | 5J | | | 3-0 | 71-51-11 | D01200J | 2 | | | GD00231 | DC.. | N | | 001-099 |
| 0001 | 18 | 5J | | | 2-0 | 71-51-11 | D01200J | 2 | | | GD00231 | DC.. | N | | 115-199 |
| 0005 | 18 | 5J | | | 3-0 | 74-31-21 | D01200J | 33 | | | GD00197 | AC.. | N | | 001-099 |
| 0005 | 18 | 5J | | | 1-10 | 74-31-21 | D01200J | 33 | | | GD00197 | AC.. | N | | 115-199 |
| 0012 | 20 | 5J | | | 12-3 | SPARE | D01200J | 4 | | | D42290P | 16 | | | ALL |
| 0018R | 20 | FV | | | 12-2 | 26-11-21 | D01210J | 2 | | | D42290P | 25 | | | ALL |
| 0019R | 20 | FV | | | 12-2 | 26-11-21 | D01210J | 8 | | | D42290P | 33 | | | ALL |
| 0020R | 20 | FV | | | 12-2 | 26-11-21 | D01210J | 14 | | | D42290P | 27 | | | ALL |
| 0021 | 18 | 5J | | | 12-2 | 26-13-21 | D01210J | 4 | | | D42290P | 28 | | | ALL |
| 0022 | 18 | 5J | | | 12-2 | 26-13-21 | D01210J | 5 | | | D42290P | 34 | | | ALL |
| 0028 | 18 | 5J | | | 3-0 | 80-11-21 | D01200J | 8 | | | GD00231 | DC.. | N | | 001-099 |
| 0028 | 18 | 5J | | | 2-0 | 80-11-21 | D01200J | 8 | | | GD00231 | DC.. | N | | 115-199 |
| 0029 | 18 | 5J | | | 3-0 | 71-51-11 | D01200J | 25 | | | GD00231 | DC.. | N | | 001-099 |
| 0029 | 18 | 5J | | | 2-0 | 71-51-11 | D01200J | 25 | | | GD00231 | DC.. | N | | 115-199 |
| 0030R | 18 | FV | | | 3-4 | 26-11-21 | D01210J | 13 | | | GD00231 | DC.. | N | | ALL |
| 0031 | 20 | 1E | | | 0-7 | 77-12-11 | D01200J | | AC | | D01200J | S/R | | | ALL |
| 0032 | 20 | 1E | | | 0-7 | 77-12-21 | D01200J | | AD | | D01200J | S/R | | | ALL |
| 0033 | 20 | 1E | | | 0-7 | 77-21-11 | D01210J | | AE | | D01210J | S/R | | | ALL |
| 0037 | 18 | 1E | | | 0-7 | 30-34-22 | D01200J | | AF | | D01200J | S/R | | | 001-099 |
| 0037 | 18 | 1E | | | 0-2 | 30-34-22 | D01200J | S/R | | | D01200J | | | AG | 115-199 |
| 1001 | 20 | 5N | AL | | 12-5 | 78-34-21 | D42290P | 32 | | | D02832 | 3 | | | ALL |
| 1001Z | | | AL | | 0-0 | 78-34-21 | D42290P | S/R | | | GD00783 | ST.. | N | * | ALL |
| 1002 | 18 | 5N | AM | | 5-0 | 78-34-21 | D02832 | 1 | | | GD00190 | DC.. | N | * | ALL |
| 1002Z | | | AM | | 0-0 | 78-34-21 | GD00783 | ST.. | N | * | GD00190 | DC.. | N | * | ALL |
| 1004 | 20 | 5N | T | | 12-3 | 74-31-21 | D01200J | 22 | | | D42290P | 15 | | | ALL |
| 1004Z | | | T | | 0-0 | 74-31-21 | D01200J | S/R | | | D42290P | S/R | | | ALL |
| 2501B | 20 | 5P | AA | | 12-3 | 77-12-11 | D01200J | 37 | | | D42290P | 5 | | | ALL |
| 2501R | 20 | 5P | AA | | 0-0 | 77-12-11 | D01200J | 36 | | | D42290P | 4 | | | ALL |
| 2501Z | | | AA | | 0-0 | 77-12-11 | D01200J | | AC | | D42290P | S/R | | | ALL |
| 2502B | 20 | 5P | AB | | 12-3 | 77-12-21 | D01200J | 39 | | | D42290P | 8 | | | ALL |
| 2502R | 20 | 5P | AB | | 0-0 | 77-12-21 | D01200J | 38 | | | D42290P | 7 | | | ALL |
| 2502Z | | | AB | | 0-0 | 77-12-21 | D01200J | | AD | | D42290P | S/R | | | ALL |
| 2503B | 20 | 5P | AF | | 12-3 | 74-31-21 | D01200J | 34 | | | D42290P | 2 | | | ALL |
| 2503R | 20 | 5P | AF | | 0-0 | 74-31-21 | D01200J | 17 | | | D42290P | 3 | | | ALL |
| 2503Z | | | AF | | 0-0 | 74-31-21 | D01200J | S/R | | | D42290P | S/R | | | ALL |
| 2504B | 20 | 5P | AG | | 12-3 | SPARE | D01200J | 10 | | | D42290P | 17 | | | ALL |

WIRE LIST

D280N032

91-21-11

Section W5200

Page 6

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|---|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5208 | 286N5208 | | | RIGHT ENGINE STRUT DISC TO RIGHT ENGINE FIREWALL (continued) | | | | | | | | | | | |
| 2504R | 20 | 5P | AG | | 0-0 | SPARE | D01200J | 11 | | | D42290P | 18 | | | ALL |
| 2504Z | | | AG | | 0-0 | SPARE | D01200J | S/R | | | D42290P | S/R | | | ALL |
| 2505B | 20 | 5P | AH | | 12-2 | SPARE | D01210J | 9 | | | D42290P | 30 | | | ALL |
| 2505R | 20 | 5P | AH | | 0-0 | SPARE | D01210J | 10 | | | D42290P | 31 | | | ALL |
| 2505Z | | | AH | | 0-0 | SPARE | D01210J | S/R | | | D42290P | S/R | | | ALL |
| 2506B | 18 | 5P | AJ | | 12-3 | 30-34-22 | D01200J | 28 | | | D42290P | 35 | | | 001-099 |
| 2506B | 18 | 5P | AK | | 12-3 | 30-34-22 | D01200J | 28 | | | D42290P | 35 | | | 115-199 |
| 2506R | 18 | 5P | AJ | | 0-0 | 30-34-22 | D01200J | 29 | | | D42290P | 36 | | | 001-099 |
| 2506R | 18 | 5P | AK | | 0-0 | 30-34-22 | D01200J | 29 | | | D42290P | 36 | | | 115-199 |
| 2506Z | | | AJ | | 0-0 | 30-34-22 | D01200J | | | AF | D42290P | S/R | | | 001-099 |
| 2506Z | | | AK | | 0-0 | 30-34-22 | D01200J | | | AG | D42290P | S/R | | | 115-199 |
| 3501B | 20 | 5Q | AE | | 12-3 | 80-11-21 | D01200J | 32 | | | D42290P | 12 | | | ALL |
| 3501R | 20 | 5Q | AE | | 0-0 | 80-11-21 | D01200J | 7 | | | D42290P | 13 | | | ALL |
| 3501Y | 20 | 5Q | AE | | 0-0 | 80-11-21 | D01200J | 9 | | | D42290P | 14 | | | ALL |
| 3501Z | | | AE | | 0-0 | 80-11-21 | D01200J | S/R | | | D42290P | S/R | | | ALL |
| 4251B | 20 | 5R | AD | | 12-3 | 79-35-11 | D01200J | 6 | | | D42290P | 11 | | | ALL |
| 4251G | 20 | 5R | AD | | 0-0 | 79-33-11 | D01200J | 16 | | | D42290P | 10 | | | ALL |
| 4251R | 20 | 5R | AD | | 0-0 | 73-33-11 | D01200J | 5 | | | D42290P | 1 | | | ALL |
| 4251Y | 20 | 5R | AD | | 0-0 | 73-34-11 | D01200J | 1 | | | D42290P | 21 | | | ALL |
| 4251Z | | | AD | | 0-0 | 79-35-11 | D01200J | S/R | | | D42290P | S/R | | | ALL |
| 4501G | 20 | DU | AC | | 12-2 | 77-21-11 | D01210J | 6 | 4B | | D42290P | 22 | | | ALL |
| 4501W | 20 | DU | AC | | 0-0 | 77-21-11 | D01210J | 7 | 4D | | D42290P | 23 | | | ALL |
| 4501Z | | | AC | | 0-0 | 77-21-11 | D01210J | | | AE | D42290P | S/R | | | ALL |
| FRAC | | | | | 0-3 | 77-12-11 | D01200J | | | AC | D01200J | 26 | | | ALL |
| FRAD | | | | | 0-3 | 77-12-21 | D01200J | | | AD | D01200J | 21 | | | ALL |
| FRAE | | | | | 0-3 | 77-21-11 | D01210J | | | AE | D01210J | 1 | | | ALL |
| FRAF | | | | | 0-0 | 30-34-22 | D01200J | | | AF | D01200J | 27 | | | 001-099 |
| FRAG | | | | | 0-0 | 30-34-22 | D01200J | 27 | | | D01200J | | | AG | 115-199 |

WIRE LIST

D280N032

91-21-11

Section W5200

Page 7 End

May 17/2006



757-200 WIRING DIAGRAM MANUAL

| Bundle No. Wire No. | Part Number | | | Description | | | From | | | | To | | | | |
|------------------------|-----------------|----|----|--|-------|----------|---------|------|------|--------|---------|------|------|--------|-------------|
| | GA | CO | TY | Fam | FT-IN | Diagram | Equip | Term | Type | Splice | Equip | Term | Type | Splice | Effectivity |
| W5214 | 286N5214 | | | R/H WING LEADING EDGE RIB TO R.ENG. F/W-R. ENG./GEN.CONTROL | | | | | | | | | | | |
| 0001 | 20 | | 5J | | 12-7 | 24-11-21 | D40028P | | 8 | | D01214J | | 8 | | ALL |
| 0002 | 16 | | 2A | | 12-7 | 24-11-21 | D40028P | | 4 | | D01214J | | 4 | | ALL |
| 0003 | 16 | | 2A | | 1-10 | 24-11-21 | D01214J | | 21 | | GD00249 | DC.. | N | | ALL |
| 0004 | 18 | | 5J | | 1-10 | 24-11-21 | D01214J | | 20 | | GD00249 | DC.. | N | | ALL |
| 0006 | 20 | | 5J | | 12-7 | SPARE | D40028P | | 25 | | D01214J | | 25 | | ALL |
| 0007 | 20 | | 5J | | 12-7 | SPARE | D40028P | | 26 | | D01214J | | 26 | | ALL |
| 2001B | 20 | | 5K | AD | 12-7 | 24-11-21 | D40028P | | 18 | | D01214J | | 18 | | ALL |
| 2001R | 20 | | 5K | AD | 0-0 | 24-11-21 | D40028P | | 19 | | D01214J | | 19 | | ALL |
| 2002B | 20 | | 5K | AE | 12-7 | 24-11-21 | D40028P | | 6 | | D01214J | | 6 | | ALL |
| 2002R | 20 | | 5K | AE | 0-0 | 24-11-21 | D40028P | | 7 | | D01214J | | 7 | | ALL |
| 2003B | 20 | | 5K | AG | 12-7 | SPARE | D40028P | | 22 | | D01214J | | 22 | | ALL |
| 2003R | 20 | | 5K | AG | 0-0 | SPARE | D40028P | | 23 | | D01214J | | 23 | | ALL |
| 2501B | 20 | | 5P | AB | 12-7 | 24-21-21 | D40028P | | 10 | | D01214J | | 10 | | ALL |
| 2501R | 20 | | 5P | AB | 0-0 | 24-21-21 | D40028P | | 9 | | D01214J | | 9 | | ALL |
| 2501Z | | | | AB | 0-0 | 24-21-21 | D40028P | | 11 | | D01214J | | 11 | | ALL |
| 2502B | 20 | | 5P | AF | 12-7 | 24-11-21 | D40028P | | 1 | | D01214J | | 1 | | ALL |
| 2502R | 20 | | 5P | AF | 0-0 | 24-11-21 | D40028P | | 2 | | D01214J | | 2 | | ALL |
| 2502Z | | | | AF | 0-0 | 24-11-21 | D40028P | | 5 | | D01214J | | 5 | | ALL |
| 3001B | 18 | | 5L | AA | 12-7 | 24-21-21 | D40028P | | 16 | | D01214J | | 16 | | ALL |
| 3001R | 18 | | 5L | AA | 0-0 | 24-21-21 | D40028P | | 15 | | D01214J | | 15 | | ALL |
| 3001Y | 18 | | 5L | AA | 0-0 | 24-21-21 | D40028P | | 17 | | D01214J | | 17 | | ALL |
| 4001B | 20 | | 5M | AC | 12-7 | 24-21-21 | D40028P | | 13 | | D01214J | | 13 | | ALL |
| 4001G | 20 | | 5M | AC | 0-0 | 24-21-21 | D40028P | | 3 | | D01214J | | 3 | | ALL |
| 4001R | 20 | | 5M | AC | 0-0 | 24-21-21 | D40028P | | 12 | | D01214J | | 12 | | ALL |
| 4001Y | 20 | | 5M | AC | 0-0 | 24-21-21 | D40028P | | 14 | | D01214J | | 14 | | ALL |

WIRE LIST

D280N032

91-21-11

Section W5210

Page 1 End

May 17/2006