

**91-21-41**

**TERMINAL STRIP LIST**



91-21-41  
 TERMINAL STRIP LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
EFFECTIVE PAGES			TB0000 cont.			TB0000 cont.		
	1 thru 8	Aug 05/2009		15	Jun 28/2006		42	Feb 06/2009
T00100	1	Jun 28/2006		16	Jun 28/2006		43	Feb 06/2009
	2	Jun 28/2006		17	Jun 28/2006		44	Feb 06/2009
	3	Jun 28/2006		18	Jun 28/2006		45	Feb 06/2009
	4	Jun 28/2006		19	Jun 28/2006		46	Feb 06/2009
	5	Jun 28/2006		20	Jun 28/2006		47	Feb 06/2009
	6	Jun 28/2006		21	Jun 28/2006		48	Feb 06/2009
	7	Jun 28/2006		22	Jun 28/2006		49	Feb 06/2009
T00200	1	Mar 09/2006		23	Jun 28/2006		50	Feb 06/2009
T00600	1	Jun 06/2008		24	Jun 28/2006		51	Feb 06/2009
T00800	1	Mar 09/2006		25	Jun 28/2006		52	Feb 06/2009
T01500	1	Mar 09/2006		26	Jun 28/2006		53	Feb 06/2009
T10000	1	Mar 09/2006		27	Jun 28/2006		54	Feb 06/2009
TB0000	1	Jun 28/2006		28	Jun 28/2006		55	Feb 06/2009
	2	Jun 28/2006		29	Jun 28/2006		56	Feb 06/2009
	3	Jun 28/2006		30	Jun 28/2006		57	Feb 06/2009
	4	Jun 28/2006		31	Jun 28/2006		58	Feb 06/2009
	5	Jun 28/2006		32	Jun 28/2006		59	Feb 06/2009
	6	Jun 28/2006		33	Jun 28/2006		60	Feb 06/2009
	7	Jun 28/2006		34	Jun 28/2006		61	Feb 06/2009
	8	Jun 28/2006		35	Feb 06/2009		62	Feb 06/2009
	9	Jun 28/2006		36	Feb 06/2009		63	Feb 06/2009
	10	Jun 28/2006		37	Feb 06/2009		64	Feb 06/2009
	11	Jun 28/2006		38	Feb 06/2009	TB0100	1	Jun 28/2006
	12	Jun 28/2006		39	Feb 06/2009		2	Jun 28/2006
	13	Jun 28/2006		40	Feb 06/2009		3	Jun 28/2006
	14	Jun 28/2006		41	Feb 06/2009		4	Jun 28/2006

A = Added, R = Revised, D = Deleted, O = Overflow

TERMINAL STRIP LIST

D280T132

EFFECTIVE PAGES

Page 1  
 Aug 05/2009



91-21-41  
TERMINAL STRIP LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
TB0100 cont.			TB0100 cont.			TB0100 cont.		
	5	Jun 28/2006		32	Jun 28/2006		59	Mar 14/2007
	6	Jun 28/2006		33	Jun 28/2006		60	Mar 14/2007
	7	Jun 28/2006		34	Jun 28/2006		61	Mar 14/2007
	8	Jun 28/2006		35	Jun 28/2006		62	Mar 14/2007
	9	Jun 28/2006		36	Jun 28/2006		63	Mar 14/2007
	10	Jun 28/2006		37	Jun 28/2006		64	Mar 14/2007
	11	Jun 28/2006		38	Jun 28/2006		65	Mar 14/2007
	12	Jun 28/2006		39	Mar 14/2007		66	Mar 14/2007
	13	Jun 28/2006		40	Mar 14/2007		67	Mar 14/2007
	14	Jun 28/2006		41	Mar 14/2007		68	Mar 14/2007
	15	Jun 28/2006		42	Mar 14/2007		69	Mar 14/2007
	16	Jun 28/2006		43	Mar 14/2007		70	Mar 14/2007
	17	Jun 28/2006		44	Mar 14/2007		71	Mar 14/2007
	18	Jun 28/2006		45	Mar 14/2007		72	Mar 14/2007
	19	Jun 28/2006		46	Mar 14/2007		73	Mar 14/2007
	20	Jun 28/2006		47	Mar 14/2007		74	Mar 14/2007
	21	Jun 28/2006		48	Mar 14/2007		75	Mar 14/2007
	22	Jun 28/2006		49	Mar 14/2007		76	Mar 14/2007
	23	Jun 28/2006		50	Mar 14/2007		77	Mar 14/2007
	24	Jun 28/2006		51	Mar 14/2007		78	Mar 14/2007
	25	Jun 28/2006		52	Mar 14/2007		79	Mar 14/2007
	26	Jun 28/2006		53	Mar 14/2007		80	Mar 14/2007
	27	Jun 28/2006		54	Mar 14/2007		81	Mar 14/2007
	28	Jun 28/2006		55	Mar 14/2007		82	Mar 14/2007
	29	Jun 28/2006		56	Mar 14/2007		83	Mar 14/2007
	30	Jun 28/2006		57	Mar 14/2007		84	Mar 14/2007
	31	Jun 28/2006		58	Mar 14/2007		85	Mar 14/2007

A = Added, R = Revised, D = Deleted, O = Overflow

TERMINAL STRIP LIST

D280T132

EFFECTIVE PAGES

Page 2  
Aug 05/2009



91-21-41  
TERMINAL STRIP LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
TB0100 cont.			TB0100 cont.			TB0100 cont.		
	86	Mar 14/2007		113	Mar 14/2007		140	Mar 14/2007
	87	Mar 14/2007		114	Mar 14/2007		141	Mar 14/2007
	88	Mar 14/2007		115	Mar 14/2007		142	Mar 14/2007
	89	Mar 14/2007		116	Mar 14/2007		143	Mar 14/2007
	90	Mar 14/2007		117	Mar 14/2007		144	Mar 14/2007
	91	Mar 14/2007		118	Mar 14/2007		145	Mar 14/2007
	92	Mar 14/2007		119	Mar 14/2007		146	Mar 14/2007
	93	Mar 14/2007		120	Mar 14/2007		147	Mar 14/2007
	94	Mar 14/2007		121	Mar 14/2007		148	Mar 14/2007
	95	Sep 04/2008		122	Mar 14/2007		149	Mar 14/2007
	96	Sep 04/2008		123	Mar 14/2007		150	Mar 14/2007
	97	Sep 04/2008		124	Mar 14/2007		151	Mar 14/2007
	98	Sep 04/2008		125	Mar 14/2007		152	Mar 14/2007
	99	Sep 04/2008		126	Mar 14/2007		153	Mar 14/2007
	100	Mar 14/2007		127	Mar 14/2007		154	Mar 14/2007
	101	Mar 14/2007		128	Mar 14/2007		155	Mar 14/2007
	102	Mar 14/2007		129	Mar 14/2007		156	Mar 14/2007
	103	Mar 14/2007		130	Mar 14/2007		157	Mar 14/2007
	104	Mar 14/2007		131	Mar 14/2007		158	Mar 14/2007
	105	Mar 14/2007		132	Mar 14/2007		159	Mar 14/2007
	106	Mar 14/2007		133	Mar 14/2007		160	Mar 14/2007
	107	Mar 14/2007		134	Mar 14/2007		161	Mar 14/2007
	108	Mar 14/2007		135	Mar 14/2007		162	Mar 14/2007
	109	Mar 14/2007		136	Mar 14/2007		163	Mar 14/2007
	110	Mar 14/2007		137	Mar 14/2007		164	Mar 14/2007
	111	Mar 14/2007		138	Mar 14/2007		165	Mar 14/2007
	112	Mar 14/2007		139	Mar 14/2007		166	Mar 14/2007

A = Added, R = Revised, D = Deleted, O = Overflow

TERMINAL STRIP LIST

D280T132

EFFECTIVE PAGES

Page 3  
Aug 05/2009



91-21-41  
 TERMINAL STRIP LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
TB0100 cont.			TB0100 cont.			TB0100 cont.		
	167	Mar 14/2007	O	194	Aug 05/2009	O	221	Aug 05/2009
	168	Mar 14/2007	O	195	Aug 05/2009	O	222	Aug 05/2009
	169	Mar 14/2007	O	196	Aug 05/2009	O	223	Aug 05/2009
	170	Mar 14/2007	O	197	Aug 05/2009	O	224	Aug 05/2009
	171	Mar 14/2007	O	198	Aug 05/2009	O	225	Aug 05/2009
	172	Mar 14/2007	O	199	Aug 05/2009	O	226	Aug 05/2009
	173	Mar 14/2007	O	200	Aug 05/2009	O	227	Aug 05/2009
	174	Mar 14/2007	O	201	Aug 05/2009	O	228	Aug 05/2009
	175	Mar 14/2007	O	202	Aug 05/2009	O	229	Aug 05/2009
	176	Mar 14/2007	O	203	Aug 05/2009	O	230	Aug 05/2009
	177	Mar 14/2007	O	204	Aug 05/2009	O	231	Aug 05/2009
	178	Mar 14/2007	O	205	Aug 05/2009	O	232	Aug 05/2009
	179	Mar 14/2007	O	206	Aug 05/2009	O	233	Aug 05/2009
	180	Mar 14/2007	R	207	Aug 05/2009	O	234	Aug 05/2009
	181	Mar 14/2007	O	208	Aug 05/2009	O	235	Aug 05/2009
	182	Mar 14/2007	O	209	Aug 05/2009	O	236	Aug 05/2009
	183	Mar 14/2007	O	210	Aug 05/2009	O	237	Aug 05/2009
	184	Mar 14/2007	O	211	Aug 05/2009	O	238	Aug 05/2009
	185	Mar 14/2007	O	212	Aug 05/2009	O	239	Aug 05/2009
	186	Mar 14/2007	O	213	Aug 05/2009	O	240	Aug 05/2009
	187	Mar 14/2007	O	214	Aug 05/2009	O	241	Aug 05/2009
	188	Mar 14/2007	O	215	Aug 05/2009	O	242	Aug 05/2009
	189	Mar 14/2007	O	216	Aug 05/2009	O	243	Aug 05/2009
O	190	Aug 05/2009	O	217	Aug 05/2009	O	244	Aug 05/2009
O	191	Aug 05/2009	O	218	Aug 05/2009	O	245	Aug 05/2009
O	192	Aug 05/2009	O	219	Aug 05/2009	O	246	Aug 05/2009
O	193	Aug 05/2009	O	220	Aug 05/2009	O	247	Aug 05/2009

A = Added, R = Revised, D = Deleted, O = Overflow

TERMINAL STRIP LIST

D280T132

EFFECTIVE PAGES

Page 4  
 Aug 05/2009



91-21-41  
TERMINAL STRIP LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
TB0100 cont.			TB0100 cont.			TB0100 cont.		
O	248	Aug 05/2009		275	Mar 14/2007		302	Mar 14/2007
O	249	Aug 05/2009		276	Mar 14/2007		303	Mar 14/2007
O	250	Aug 05/2009		277	Mar 14/2007		304	Mar 14/2007
O	251	Aug 05/2009		278	Mar 14/2007		305	Mar 14/2007
O	252	Aug 05/2009		279	Mar 14/2007		306	Mar 14/2007
O	253	Aug 05/2009		280	Mar 14/2007		307	Mar 14/2007
O	254	Aug 05/2009		281	Mar 14/2007		308	Mar 14/2007
O	255	Aug 05/2009		282	Mar 14/2007		309	Mar 14/2007
O	256	Aug 05/2009		283	Mar 14/2007		310	Mar 14/2007
O	257	Aug 05/2009		284	Mar 14/2007		311	Mar 14/2007
O	258	Aug 05/2009		285	Mar 14/2007		312	Feb 06/2009
O	259	Aug 05/2009		286	Mar 14/2007		313	Feb 06/2009
O	260	Aug 05/2009		287	Mar 14/2007		314	Feb 06/2009
O	261	Aug 05/2009		288	Mar 14/2007		315	Feb 06/2009
O	262	Aug 05/2009		289	Mar 14/2007		316	Feb 06/2009
O	263	Aug 05/2009		290	Mar 14/2007		317	Feb 06/2009
O	264	Aug 05/2009		291	Mar 14/2007		318	Feb 06/2009
O	265	Aug 05/2009		292	Mar 14/2007		319	Feb 06/2009
O	266	Aug 05/2009		293	Mar 14/2007		320	Feb 06/2009
O	267	Aug 05/2009		294	Mar 14/2007		321	Feb 06/2009
O	268	Aug 05/2009		295	Mar 14/2007		322	Feb 06/2009
O	269	Aug 05/2009		296	Mar 14/2007		323	Feb 06/2009
O	270	Aug 05/2009		297	Mar 14/2007		324	Feb 06/2009
O	271	Aug 05/2009		298	Mar 14/2007		325	Feb 06/2009
	272	Mar 14/2007		299	Mar 14/2007		326	Feb 06/2009
	273	Mar 14/2007		300	Mar 14/2007		327	Feb 06/2009
	274	Mar 14/2007		301	Mar 14/2007		328	Feb 06/2009

A = Added, R = Revised, D = Deleted, O = Overflow

TERMINAL STRIP LIST

D280T132

EFFECTIVE PAGES

Page 5  
Aug 05/2009



91-21-41  
 TERMINAL STRIP LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
TB0100 cont.			TB0200 cont.			TB0200 cont.		
	329	Feb 06/2009	O	21	Aug 05/2009		48	Feb 06/2009
	330	Feb 06/2009	O	22	Aug 05/2009		49	Feb 06/2009
	331	Mar 14/2007		23	Feb 06/2009		50	Feb 06/2009
	332	Mar 14/2007		24	Feb 06/2009		51	Feb 06/2009
	333	Mar 14/2007		25	Feb 06/2009		52	Feb 06/2009
	334	Mar 14/2007		26	Feb 06/2009		53	Feb 06/2009
	335	Mar 14/2007		27	Feb 06/2009		54	Feb 06/2009
TB0200	1	Jun 28/2006		28	Feb 06/2009		55	Feb 06/2009
	2	Jun 28/2006		29	Feb 06/2009		56	Feb 06/2009
	3	Jun 28/2006		30	Feb 06/2009		57	Feb 06/2009
	4	Jun 28/2006		31	Feb 06/2009		58	Feb 06/2009
	5	Jun 28/2006		32	Feb 06/2009		59	Feb 06/2009
	6	Jun 28/2006		33	Feb 06/2009		60	Feb 06/2009
	7	Jun 28/2006		34	Feb 06/2009		61	Feb 06/2009
	8	Jun 28/2006		35	Feb 06/2009		62	Feb 06/2009
	9	Jun 28/2006		36	Feb 06/2009		63	Feb 06/2009
	10	Jun 28/2006		37	Feb 06/2009		64	Feb 06/2009
	11	Feb 06/2009		38	Feb 06/2009		65	Feb 06/2009
	12	Feb 06/2009		39	Feb 06/2009		66	Feb 06/2009
	13	Feb 06/2009		40	Feb 06/2009		67	Feb 06/2009
	14	Feb 06/2009		41	Feb 06/2009		68	Feb 06/2009
	15	Feb 06/2009		42	Feb 06/2009		69	Feb 06/2009
	16	Feb 06/2009		43	Feb 06/2009		70	Feb 06/2009
R	17	Aug 05/2009		44	Feb 06/2009		71	Feb 06/2009
R	18	Aug 05/2009		45	Feb 06/2009		72	Feb 06/2009
O	19	Aug 05/2009		46	Feb 06/2009		73	Feb 06/2009
O	20	Aug 05/2009		47	Feb 06/2009		74	Feb 06/2009

A = Added, R = Revised, D = Deleted, O = Overflow

TERMINAL STRIP LIST

D280T132

EFFECTIVE PAGES

Page 6  
 Aug 05/2009



91-21-41  
 TERMINAL STRIP LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
TB0200 cont.			TB0300 cont.			TB5000	1	Feb 06/2009
	75	Feb 06/2009		13	Feb 06/2009		2	Feb 06/2009
	76	Feb 06/2009		14	Feb 06/2009		3	Feb 06/2009
	77	Feb 06/2009		15	Feb 06/2009		4	Feb 06/2009
	78	Feb 06/2009		16	Feb 06/2009		5	Feb 06/2009
	79	Feb 06/2009		17	Feb 06/2009		6	Feb 06/2009
	80	Feb 06/2009		18	Feb 06/2009		7	Feb 06/2009
	81	Feb 06/2009		19	Feb 06/2009	TB5100	1	Feb 06/2009
	82	Feb 06/2009		20	Feb 06/2009		2	Feb 06/2009
	83	Feb 06/2009		21	Feb 06/2009		3	Feb 06/2009
	84	Feb 06/2009		22	Feb 06/2009		4	Feb 06/2009
	85	Feb 06/2009		23	Feb 06/2009		5	Feb 06/2009
	86	Feb 06/2009		24	Feb 06/2009		6	Feb 06/2009
	87	Feb 06/2009		25	Feb 06/2009	TB9000	1	Feb 06/2009
	88	Feb 06/2009		26	Feb 06/2009	R TS0000	1	Aug 05/2009
	89	Feb 06/2009		27	Feb 06/2009		2	Feb 06/2009
TB0300	1	Feb 06/2009		28	Feb 06/2009		3	Feb 06/2009
	2	Feb 06/2009		29	Feb 06/2009	R TS0100	1	Aug 05/2009
	3	Feb 06/2009		30	Feb 06/2009		2	Feb 06/2009
	4	Feb 06/2009		31	Feb 06/2009		3	Feb 06/2009
	5	Feb 06/2009		32	Feb 06/2009	TS0200	1	Feb 06/2009
	6	Feb 06/2009		33	Feb 06/2009		2	Feb 06/2009
	7	Feb 06/2009	TB0400	1	Feb 06/2009		3	Feb 06/2009
	8	Feb 06/2009		2	Feb 06/2009		4	Feb 06/2009
	9	Feb 06/2009		3	Feb 06/2009	TS0300	1	Feb 06/2009
	10	Feb 06/2009		4	Feb 06/2009		2	Feb 06/2009
	11	Feb 06/2009		5	Feb 06/2009		3	Feb 06/2009
	12	Feb 06/2009		6	Feb 06/2009	TS0400	1	Feb 06/2009

A = Added, R = Revised, D = Deleted, O = Overflow

TERMINAL STRIP LIST

D280T132

EFFECTIVE PAGES

Page 7  
 Aug 05/2009





91-21-41  
TERMINAL STRIP LIST

Section	Page	Date	Section	Page	Date	Section	Page	Date
TS0400 cont.								
	2	Feb 06/2009						
TS0500	1	Feb 06/2009						
	2	Feb 06/2009						
TS0600	1	Feb 06/2009						
TS5000	1	Feb 06/2009						
TS5100	1	Feb 06/2009						
	2	BLANK						

A = Added, R = Revised, D = Deleted, O = Overflow

TERMINAL STRIP LIST

D280T132

**EFFECTIVE PAGES**

Page 8  
Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
T00101		<b>S282T001-1</b>					<b>SHELF/E03/02</b>		<b>ALL</b>
		+	H	W0266	001	02		24-32-11	ALL
		-	G5	W0266	002	02		24-32-11	ALL
T00102		<b>S282T001-1</b>					<b>SHELF/E03/02</b>		<b>ALL</b>
		+	H	W0268	001	02		24-32-11	ALL
		-	G5	W0268	002	02		24-32-11	ALL
T00103		<b>10-60011-2</b>					<b>P034-00/ /</b>		<b>ALL</b>
		+	D	W1012	005	10		24-54-61	ALL
		-	D	W1012	004	10		24-54-61	ALL
		A	C	W1012	001	22		24-54-61	ALL
		B	C	W1012	002	22		24-54-61	ALL
		C	C	W1012	003	22		24-54-61	ALL
		N	C	W1012	015	20		24-54-61	ALL
T00105		<b>S281T001-4</b>					<b>P031-00/ /</b>		<b>ALL</b>
T00106		<b>S281T001-4</b>					<b>P006-03/ /</b>		<b>ALL</b>
T00107		<b>S281T001-4</b>					<b>P032-00/ /</b>		<b>ALL</b>
T00108		<b>S281T001-4</b>					<b>P006-04/ /</b>		<b>ALL</b>
T00111		<b>S281T001-4</b>					<b>P034-00/ /</b>		<b>ALL</b>
T00112		<b>S281T001-4</b>					<b>P031-00/ /</b>		<b>ALL</b>
T00113		<b>S281T001-4</b>					<b>P032-00/ /</b>		<b>ALL</b>
T00115		<b>S281T001-4</b>					<b>P034-00/ /</b>		<b>ALL</b>
T00116		<b>S281T001-4</b>					<b>P034-00/ /</b>		<b>ALL</b>
T00122		<b>S281T001-4</b>					<b>P034-00/ /</b>		<b>ALL</b>
T00123		<b>60B40026-14</b>					<b>P006-03/ /</b>		<b>ALL</b>
		DED		W1026	011Z			24-53-11	ALL
		GND	E	W1026	012	16		24-53-11	ALL
		GND	E	W1026	078	16		24-53-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T00100

Page 1

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>T00123</b>		<b>60B40026-14 (continued)</b>					<b>P006-03/ /</b>		<b>ALL</b>
		HV	E	W1026	011	16		24-53-11	ALL
		LV	E	W1026	010	10		24-53-11	ALL
<b>T00124</b>		<b>60B40026-14</b>					<b>P006-04/ /</b>		<b>ALL</b>
		GND	E	W1030	013	16		24-53-21	ALL
		GND	E	W1030	051	16		24-53-21	ALL
		HV	E	W1030	012	16		24-53-21	ALL
		LV	E	W1030	011	10		24-53-21	ALL
<b>T00126</b>		<b>60B40026-13</b>					<b>P033-00/ /</b>		<b>ALL</b>
		GND	N	W0138	048	10		24-53-51	ALL
		HV	N	W0138	046	12		24-53-51	ALL
		LV	N	W0138	049	10		24-53-51	ALL
<b>T00127</b>		<b>S281T001-4</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>T00128</b>		<b>S281T001-4</b>					<b>P032-00/ /</b>		<b>ALL</b>
<b>T00129</b>		<b>60B40026-17</b>					<b>0763/148/L073</b>		<b>ALL</b>
		GND	E	W0602	081	12		33-42-11	ALL
		HV1	E	W0602	080	20		33-42-11	050-099
		HV1	E	W0602	080	16		33-42-11	150-199, 275-299
		HV3	E	W0602	079	18		33-42-11	050-099
		HV3	E	W0602	079	16		33-42-11	150-199, 275-299
		LV	E	W0602	082	12		33-42-11	ALL
<b>T00130</b>		<b>60B40026-17</b>					<b>0763/150/R075</b>		<b>050-099</b>
<b>T00130</b>		<b>60B40026-17</b>					<b>0763/148/R073</b>		<b>150-199, 275-299</b>
		GND	E	W0656	076	12		33-42-11	ALL
		HV1	E	W0656	075	20		33-42-11	050-099
		HV1	E	W0656	075	16		33-42-11	150-199, 275-299
		HV3	E	W0656	074	18		33-42-11	050-099
		HV3	E	W0656	074	16		33-42-11	150-199, 275-299
		LV	E	W0656	077	12		33-42-11	ALL
<b>T00131</b>		<b>FT1246</b>					<b>L1128/12/TIP</b>		<b>ALL</b>
<b>T00132</b>		<b>FT1246</b>					<b>R1128/12/TIP</b>		<b>ALL</b>
<b>T00137</b>		<b>60B40026-20</b>					<b>0763/150/L075</b>		<b>ALL</b>

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T00100

Page 2

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>T00138</b>		<b>60B40026-20</b>					<b>0766/150/R075</b>		<b>050-099</b>
<b>T00138</b>		<b>60B40026-20</b>					<b>0762/150/R074</b>		<b>150-199, 275-299</b>
<b>T00139</b>		<b>10615</b>					<b>P036-00/ /</b>		<b>ALL</b>
		GND	D	W0184	770	22		34-12-11	ALL
		HV	D	W0184	771	22		34-12-11	ALL
		LV	D	W0184	769	22		34-12-11	ALL
<b>T00140</b>		<b>10615</b>					<b>P037-00/ /</b>		<b>ALL</b>
		GND	D	W0192	108	22		34-12-21	ALL
		HV	D	W0192	106	22		34-12-21	ALL
		LV	D	W0192	107	22		34-12-21	ALL
<b>T00141</b>		<b>60B40026-16</b>					<b>0980/192/R055</b>		<b>ALL</b>
		GND	E	W0628	024	16		33-31-11	ALL
		HV2	E	W0628	023	20		33-31-11	ALL
		LV	E	W0628	025	16		33-31-11	ALL
		LV	E	W0628	026	16		33-31-11	ALL
<b>T00143</b>		<b>FT1219</b>					<b>P023-00/ /</b>		<b>ALL</b>
		BLK		W1194	B-A			33-42-11	ALL
		BRN		W1194	B-F			33-42-11	ALL
		CAP	Y	W1194	B-C			33-42-11	ALL
		CAP	Y	W1194	B-E			33-42-11	ALL
		GRA		W1194	B-B			33-42-11	ALL
		GRO		W1194	B-D			33-42-11	ALL
		GRR		W1194	B-E			33-42-11	ALL
		GRY		W1194	B-C			33-42-11	ALL
<b>T00144</b>		<b>FT1219</b>					<b>P023-00/ /</b>		<b>ALL</b>
		BLK		W1194	A-A			33-42-11	ALL
		BRN		W1194	A-F			33-42-11	ALL
		CAP	Y	W1194	A-C			33-42-11	ALL
		CAP	Y	W1194	A-E			33-42-11	ALL
		GRA		W1194	A-B			33-42-11	ALL
		GRO		W1194	A-D			33-42-11	ALL
		GRR		W1194	A-E			33-42-11	ALL
		GRY		W1194	A-C			33-42-11	ALL
<b>T00146</b>		<b>60B40026-19</b>					<b>0843/114/L010</b>		<b>ALL</b>

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T00100

Page 3

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>T00148</b>		<b>60B40026-17</b>					<b>P035-00/ /</b>		<b>ALL</b>
		GND	E	W1066	051	12		33-37-11	ALL
		HV1	E	W1066	049	18		33-37-11	050-099
		HV1	E	W1066	049	16		33-37-11	150-199, 275-299
		HV1	E	W1066	050	18		33-37-11	050-099
		HV1	E	W1066	050	16		33-37-11	150-199, 275-299
		HV1	E	W1066	065	18		33-37-11	050-099
		HV1	E	W1066	065	16		33-37-11	150-199, 275-299
		LV	E	W1066	052	12		33-37-11	ALL
<b>T00149</b>		<b>60B40026-19</b>					<b>1831/242/R038</b>		<b>ALL</b>
<b>T00150</b>		<b>60B40026-19</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>T00151</b>		<b>60B40026-16</b>					<b>P039-00/ /</b>		<b>ALL</b>
		GND	E	W1068	059	16		33-31-61	ALL
		HV1	E	W1068	058	20		33-31-61	ALL
		LV	E	W1068	060	16		33-31-61	ALL
<b>T00152</b>		<b>60B40026-17</b>					<b>P039-00/ /</b>		<b>ALL</b>
		GND	E	W1068	051	12		33-37-21	ALL
		HV1	E	W1068	050	18		33-37-21	050-099
		HV1	E	W1068	050	16		33-37-21	150-199, 275-299
		HV1	E	W1068	067	18		33-37-21	050-099
		HV1	E	W1068	067	16		33-37-21	150-199, 275-299
		LV	E	W1068	052	12		33-37-21	ALL
<b>T00153</b>		<b>60B40026-19</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>T00177</b>		<b>60B40026-20</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>T00180</b>		<b>60B40026-15</b>					<b>P019-00/ /</b>		<b>ALL</b>
		GND	E	W1104	052	16		33-21-11	ALL
		HV2	E	W1104	596	20		33-21-11	050-099, 275-299
		HV2	E	W1104	618	20		33-21-11	275-299
		HV2	E	W1104	619	20		33-21-11	150-199, 275-299
		HV3	E	W1104	001	20		33-21-11	ALL
		LV	E	W1104	051	16		33-21-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T00100

Page 4

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>T00181</b>		<b>60B40026-15</b>					<b>P025-00/ /</b>		<b>ALL</b>
		GND	E	W1108	031	16		33-21-12	ALL
		HV2	E	W1108	009	20		33-21-12	150-199, 275-299
		HV2	E	W1108	600	20		33-21-12	050-099, 150-199
		HV2	E	W1108	648	20		33-21-12	275-299
		HV3	E	W1108	005	20		33-21-12	ALL
		HV3	E	W1108	138	20		33-21-12	ALL
		LV	E	W1108	002	16		33-21-12	ALL
<b>T00182</b>		<b>60B40026-15</b>					<b>P025-00/ /</b>		<b>ALL</b>
		GND	E	W1108	014	16		33-21-12	ALL
		HV2	E	W1108	021	20		33-21-12	150-199, 275-299
		HV2	E	W1108	627	20		33-21-12	050-099, 150-199
		HV2	E	W1108	650	20		33-21-12	275-299
		HV3	E	W1108	013	20		33-21-12	ALL
		HV3	E	W1108	089	20		33-21-12	ALL
		LV	E	W1108	001	16		33-21-12	ALL
<b>T00183</b>		<b>60B40026-15</b>					<b>P019-00/ /</b>		<b>ALL</b>
		GND	E	W1104	058	18		33-21-31	050-099
		GND	E	W1104	058	16		33-21-31	150-199, 275-299
		HV2	E	W1104	057	20		33-21-31	ALL
		HV2	E	W1104	146	20		33-21-31	ALL
		HV2	E	W1104	603	20		33-21-31	150-199
		LV	E	W1104	055	18		33-21-31	050-099
		LV	E	W1104	055	16		33-21-31	150-199, 275-299
		LV	E	W1104	061	16		33-21-31	275-299
		LV	E	W1104	094	18		33-21-31	050-099
		LV	E	W1104	094	16		33-21-31	150-199, 280-299
		LV	E	W1104	627	16		33-21-31	275-278
		LV	E	W1104	801	18		33-21-31	050-099
		LV	E	W1104	801	16		33-21-31	162-199
<b>T00184</b>		<b>60B40026-15</b>					<b>P019-00/ /</b>		<b>ALL</b>
		GND	E	W1104	099	18		33-21-31	050-099
		GND	E	W1104	099	16		33-21-31	150-199, 275-299
		HV2	E	W1104	098	20		33-21-31	ALL
		LV	E	W1104	056	18		33-21-31	050-099
		LV	E	W1104	056	16		33-21-31	150-199, 275-299
		LV	E	W1104	094	16		33-21-31	275-278

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T00100

Page 5

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>T00184</b>		<b>60B40026-15 (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
		LV	E	W1104	627	18		33-21-31	050-099
		LV	E	W1104	627	16		33-21-31	150-199, 280-299
<b>T00186</b>		<b>284T1174-1</b>					<b>P035-00/ /</b>		<b>ALL</b>
		GND	E	W1066	059	16		33-31-61	ALL
		HV1	E	W1066	058	20		33-31-61	ALL
		LV	E	W1066	060	16		33-31-61	ALL
<b>T00187</b>		<b>FT1219</b>					<b>P023-00/ /</b>		<b>ALL</b>
		BLK		W1194	D-A			33-42-21	ALL
		BRN		W1194	D-F			33-42-21	ALL
		CAP	Y	W1194	D-C			33-42-21	ALL
		CAP	Y	W1194	D-E			33-42-21	ALL
		GRA		W1194	D-B			33-42-21	ALL
		GRO		W1194	D-D			33-42-21	ALL
		GRR		W1194	D-E			33-42-21	ALL
		GRY		W1194	D-C			33-42-21	ALL
<b>T00188</b>		<b>FT1219</b>					<b>P023-00/ /</b>		<b>ALL</b>
		BLK		W1194	C-A			33-42-21	ALL
		BRN		W1194	C-F			33-42-21	ALL
		CAP	Y	W1194	C-C			33-42-21	ALL
		CAP	Y	W1194	C-E			33-42-21	ALL
		GRA		W1194	C-B			33-42-21	ALL
		GRO		W1194	C-D			33-42-21	ALL
		GRR		W1194	C-E			33-42-21	ALL
		GRY		W1194	C-C			33-42-21	ALL
<b>T00189</b>		<b>60B40104-2</b>					<b>SHELF/E06/02</b>		<b>275-299</b>
		+	R	W0246	010	*1		24-32-41	275-299
		-	R	W0246	009	*1		24-32-41	275-299
<b>T00191</b>		<b>60B40026-19</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>T00193</b>		<b>60B40026-16</b>					<b>P006-03/ /</b>		<b>ALL</b>
		GND	E	W1026	066	16		24-51-14	ALL
		HV2	E	W1026	064	20		24-51-14	ALL
		LV	E	W1026	065	18		24-51-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T00100

Page 6

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>T00194</b>		<b>60B40026-16</b>					<b>P006-04/ /</b>		<b>ALL</b>
		GND	E	W0048	086	16		24-51-24	ALL
		HV2	E	W0048	085	22		24-51-24	ALL
		LV	E	W0048	087	18		24-51-24	ALL

**TERMINAL STRIP LIST**

D280T132

**91-21-41**

Section T00100

Page 7 End

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
T00232		0077CC					SHELF/E01/04		ALL
T00233		60B40026-20					P025-00/ /		050-099, 150-199

---

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T00200

Page 1 End

Mar 09/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
T00675		S332T006-13					ENG/ /		ALL
T00675		S332T006-11					ENG/ /		ALL
T00677		S332T304-1					ENG/ /		ALL
T00679		S332T305-8					ENG/ /		ALL
T00688		51A020					ENG/ /		ALL
T00689		1A6714					N178/069/R008		ALL
T00690		53T903					N161/075/L017		ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section T00600

Page 1 End

Jun 06/2008



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
T00867		P-WSUPPLIED					70.41 / /		ALL

---

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T00800

Page 1 End

Mar 09/2006



Terminal No.	Fix	Part Number		Type	Bundle	Wire No.	GA	Station / WL / BL		Diagram	Effectivity
		Term						CO			
T01519		50R241AND50R453						ENG /			ALL

**TERMINAL STRIP LIST**

D280T132

**91-21-41**

Section T01500

Page 1 End

Mar 09/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
T10033		S315N401-1					ENG / /		ALL
T10035		S315N401-1					ENG / /		ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section T10000

Page 1 End

Mar 09/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0014		<b>BACT44A0460D</b>					<b>P006-01/ /</b>		<b>ALL</b>
TB0014	<b>F</b>	<b>BACM15C1A</b>					<b>P006-01/ /</b>		<b>ALL</b>
TB0014	<b>G</b>	<b>BACM15C1B</b>					<b>P006-01/ /</b>		<b>ALL</b>
	G	11	2	W0028	088	22		24-51-31	ALL
	G	11	2	W0028	089	22		24-51-31	ALL
	G	11	2	W1040	022	22		24-51-31	ALL
	G	12	2	W0028	603	18		24-51-31	ALL
	G	12	2	W0028	606	18		24-51-31	ALL
	G	12	2	W0028	608	18		24-51-31	ALL
	G	13	2	W0028	174	24		24-33-11	ALL
	G	13	2	W0028	175	24		24-33-11	ALL
	G	13	2	W1040	045	24		24-33-11	ALL
	G	14	2	W0028	173	24		24-33-11	ALL
	G	14	2	W0028	176	24		24-33-11	ALL
	G	14	2	W1040	046	24		24-33-11	ALL
	G	5	2	W0028	141	24		24-34-11	ALL
	G	5	2	W0028	148	24		24-33-11	ALL
	G	5	2	W0028	150	24		24-34-11	ALL
	G	6	2	W0028	011	24		24-33-11	ALL
	G	6	2	W0028	012	24		24-33-11	ALL
	G	6	2	W0028	014	24		24-33-11	ALL
	G	9	2	W0028	104	22		24-51-31	ALL
	G	9	2	W0028	195	24		24-51-31	ALL
	G	9	2	W1040	042	24		24-51-31	ALL
	F	A004	2	W0028	019	24		24-33-11	ALL
	F	A004	2	W1040	034	24		24-33-11	ALL
	F	A008	2	W0028	135	18		24-51-31	ALL
	F	A008	2	W1040	021	18		24-51-31	ALL
	F	A015	2	W0048	057	24		24-51-43	ALL
	F	A015	2	W0048	069	24		24-51-43	ALL
	F	A016	2	W0048	059	24		24-51-43	ALL
	F	A016	2	W1026	059	24		24-51-43	ALL
	F	A017	2	W0048	081	24		24-51-42	ALL
	F	A017	2	W1026	050	24		24-51-42	ALL
	F	C003	2	W0028	130	18		24-33-11	ALL
	F	C003	2	W1040	033	20		24-33-11	ALL
	F	C015	2	W0048	058	24		24-51-43	ALL
	F	C015	2	W0048	071	24		24-51-43	ALL
	F	C016	2	W0028	193	24		24-51-43	ALL
	F	C016	2	W0048	074	24		24-51-43	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 1

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0016		<b>BACT44A0460D</b>					<b>P006-03/ /</b>		<b>ALL</b>
TB0016	<b>F</b>	<b>BACM15C1A</b>					<b>P006-03/ /</b>		<b>ALL</b>
TB0016	<b>X</b>	<b>BACM15C3A</b>					<b>P006-03/ /</b>		<b>ALL</b>
TB0016	<b>Y</b>	<b>BACM15C3B</b>					<b>P006-03/ /</b>		<b>ALL</b>
TB0016	<b>Z</b>	<b>BACM15C3C</b>					<b>P006-03/ /</b>		<b>ALL</b>
	Z	10	BJ	W0028	146	24		24-34-11	ALL
	Z	10	BJ	W0028	158	24		24-34-11	ALL
	Z	10	BJ	W0028	159	24		24-34-11	ALL
	Z	10	BJ	W0028	161	24		24-34-11	ALL
	Z	10	BJ	W0028	162	24		24-34-11	ALL
	F	A001	2	W0028	095	18		24-51-31	ALL
	F	A001	2	W1026	013	18		24-51-31	ALL
	Y	A002	BJ	W0028	097	22		24-51-31	ALL
	Y	A002	BJ	W1026	014	22		24-51-31	ALL
	Y	A003	BJ	W0028	098	22		24-51-31	050-099, 155-199, 277-299
	Y	A003	BJ	W0028	609	22		24-51-31	050-099, 155-199, 277-299
	Y	A003	BJ	W0046	036	22		24-51-31	050-099, 155-199, 277-299
	Y	A004	BJ	W0028	109	24		24-51-31	050-099, 155-199, 277-299
	Y	A004	BJ	W0028	605	24		24-51-31	050-099, 155-199, 277-299
	Y	A004	BJ	W0028	611	24		24-51-31	050-099, 155-199, 277-299
	Y	A005	BJ	W0028	604	24		24-51-31	150-154, 275-276
	Y	A005	BJ	W0028	610	24		24-51-31	150-154, 275-276
	Y	A005	BJ	W0028	612	24		24-51-31	150-154, 275-276
	F	A006	2	W0046	047	24		24-51-42	ALL
	F	A006	2	W1026	046	24		24-51-42	ALL
	F	A007	2	W0028	151	18		25-29-11	ALL
	F	A007	2	W0048	031	18		25-29-11	ALL
	X	A009	BJ	W0046	049	24		24-51-42	ALL
	X	A009	BJ	W1030	045	24		24-51-42	ALL
	Y	A012	BJ	W0028	166	24		24-34-11	ALL
	Y	A012	BJ	W0028	168	24		24-34-11	ALL
	Y	A012	BJ	W0028	171	24		24-34-11	ALL
	Y	A013	BJ	W0028	072	24		24-32-11	155-199
	Y	A013	BJ	W0028	098	22		24-51-31	150-154, 275-276
	Y	A013	BJ	W0028	149	24		24-32-11	155-199
	Y	A013	BJ	W0028	609	22		24-51-31	150-154, 275-276
	Y	A013	BJ	W0046	036	22		24-51-31	150-154, 275-276
	X	B008	BJ	W0028	033	24		24-28-11	ALL
	X	B008	BJ	W0046	037	24		24-28-11	ALL
	X	B009	BJ	W0028	024	24		24-34-11	ALL
	X	B009	BJ	W1030	046	24		24-34-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 2

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0016		<b>BACT44A0460D (continued)</b>					<b>P006-03/ /</b>		<b>ALL</b>
TB0016	F	<b>BACM15C1A (continued)</b>					<b>P006-03/ /</b>		<b>ALL</b>
TB0016	X	<b>BACM15C3A (continued)</b>					<b>P006-03/ /</b>		<b>ALL</b>
TB0016	Y	<b>BACM15C3B (continued)</b>					<b>P006-03/ /</b>		<b>ALL</b>
TB0016	Z	<b>BACM15C3C (continued)</b>					<b>P006-03/ /</b>		<b>ALL</b>
	Y	C002	BJ	W0028	077	24		24-33-11	ALL
	Y	C002	BJ	W0028	127	24		24-33-11	ALL
	Y	C002	BJ	W1026	038	24		24-33-11	ALL
	Y	C003	BJ	W0028	604	24		24-51-31	050-099, 155-199, 277-299
	Y	C003	BJ	W0028	610	24		24-51-31	050-099, 155-199, 277-299
	Y	C003	BJ	W0028	612	24		24-51-31	050-099, 155-199, 277-299
	Y	C005	BJ	W0028	192	24		24-51-42	ALL
	Y	C005	BJ	W0048	080	24		24-51-42	ALL
	Y	C005	BJ	W1026	056	24		24-51-42	ALL
	F	C006	2	W0046	048	24		24-51-42	ALL
	F	C006	2	W1026	048	22		24-51-42	ALL
	F	C007	2	W0028	152	22		25-29-11	ALL
	F	C007	2	W0048	042	22		25-29-11	ALL
	X	C008	BJ	W0028	025	24		24-34-11	ALL
	X	C008	BJ	W1026	036	24		24-34-11	ALL
	X	C009	BJ	W0028	070	24		24-32-11	ALL
	X	C009	BJ	W1030	047	24		24-32-11	ALL
	Y	C012	BJ	W0028	057	24		22-11-32	ALL
	Y	C012	BJ	W1026	039	24		22-11-32	ALL
	Y	C013	BJ	W0028	109	24		24-51-31	150-154, 275-276
	Y	C013	BJ	W0028	605	24		24-51-31	150-154, 275-276
	Y	C013	BJ	W0028	611	24		24-51-31	150-154, 275-276
	X	D008	BJ	W0028	074	24		24-32-11	ALL
	X	D008	BJ	W1026	037	24		24-32-11	ALL
	X	D009	BJ	W0028	072	24		24-32-11	150-154
	X	D009	BJ	W0028	149	24		24-32-11	150-154
	F	DED		W0028	095Z			24-51-31	ALL
	Y	DED		W0028	097Z			24-51-31	ALL
	F	DED		W0028	151Z			25-29-11	ALL
	F	DED		W0028	152Z			25-29-11	ALL
	Y	DED		W0046	036Z			24-51-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 3

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0018		<b>BACT44A0460D</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>F</b>	<b>BACM15C1A</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>X</b>	<b>BACM15C3A</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>Y</b>	<b>BACM15C3B</b>					<b>P006-00/ /</b>		<b>ALL</b>
TB0018	<b>Z</b>	<b>BACM15C3C</b>					<b>P006-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W0148	006	24		33-16-11	ALL
	Z	10	BJ	W0152	004	24		33-16-11	ALL
	Z	10	BJ	W0156	028	24		33-16-11	ALL
	Z	10	BJ	W0156	030	24		33-16-11	ALL
	Z	11	BJ	W0148	011	24		33-16-11	ALL
	Z	11	BJ	W0148	012	24		33-16-11	ALL
	Z	11	BJ	W0152	008	24		33-16-11	ALL
	Z	11	BJ	W0156	043	24		33-16-11	ALL
	Z	12	BJ	W0148	002	24		33-16-11	ALL
	Z	12	BJ	W0148	003	24		33-16-11	ALL
	Z	12	BJ	W0148	014	24		33-16-11	ALL
	Z	12	BJ	W0148	061	24		33-16-11	ALL
	Z	12	BJ	W0156	034	24		33-16-11	ALL
	Z	12	BJ	W0156	035	24		33-16-11	ALL
	Z	12	BJ	W0156	071	22		33-16-21	ALL
	Z	9	BJ	W0148	005	24		33-16-11	ALL
	Z	9	BJ	W0152	003	24		33-16-11	ALL
	Z	9	BJ	W0156	027	24		33-16-11	ALL
	Z	9	BJ	W0156	029	24		33-16-11	ALL
	Z	9	BJ	W0156	031	24		33-16-11	ALL
	Z	9	BJ	W0156	166	24		33-16-11	ALL
	Z	9	BJ	W0156	170	22		33-16-21	ALL
	X	A002	BJ	W0148	016	22		33-16-12	ALL
	X	A002	BJ	W0150	006	22		33-16-12	ALL
	Y	A003	BJ	W0148	043	22		33-16-21	ALL
	Y	A003	BJ	W0152	028	22		33-16-21	ALL
	Y	A003	BJ	W0156	067	22		33-16-21	ALL
	Y	A003	BJ	W0156	170	22		33-16-21	ALL
	Y	A004	BJ	W0148	001	24		33-11-11	ALL
	Y	A004	BJ	W0156	001	24		33-11-11	ALL
	Y	A004	BJ	W0158	002	24		33-11-11	ALL
	Y	A005	BJ	W0156	002	24		33-11-11	ALL
	Y	A005	BJ	W0156	005	24		33-11-11	ALL
	Y	A005	BJ	W0156	007	24		33-11-11	ALL
	Y	A006	BJ	W0156	022	24		33-11-15	ALL
	Y	A006	BJ	W0156	023	24		33-11-15	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 4

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity	
TB0018		<b>BACT44A0460D (continued)</b>						<b>P006-05/ /</b>		<b>ALL</b>
TB0018	F	<b>BACM15C1A (continued)</b>						<b>P006-05/ /</b>		<b>ALL</b>
TB0018	X	<b>BACM15C3A (continued)</b>						<b>P006-05/ /</b>		<b>ALL</b>
TB0018	Y	<b>BACM15C3B (continued)</b>						<b>P006-00/ /</b>		<b>ALL</b>
TB0018	Z	<b>BACM15C3C (continued)</b>						<b>P006-00/ /</b>		<b>ALL</b>
	Y	A006	BJ	W0156	025	24		33-11-15	ALL	
	Y	A006	BJ	W0158	009	24		33-11-15	ALL	
	Y	A007	BJ	W0148	047	22		33-16-21	ALL	
	Y	A007	BJ	W0152	033	22		33-16-21	ALL	
	Y	A007	BJ	W0156	072	22		33-16-21	ALL	
	Y	A007	BJ	W0156	074	22		33-16-21	ALL	
	F	A013	2	W0150	023	16		33-13-18	ALL	
	F	A013	2	W0156	174	16		33-13-18	ALL	
	Y	A014	BJ	W0148	017	22		33-16-12	ALL	
	Y	A014	BJ	W0150	002	22		33-16-12	ALL	
	Y	A014	BJ	W0150	007	22		33-16-12	ALL	
	Y	A015	BJ	W0148	019	22		33-16-12	ALL	
	Y	A015	BJ	W0148	020	22		33-16-12	ALL	
	Y	A015	BJ	W0148	022	22		33-16-12	ALL	
	Y	A015	BJ	W0148	023	22		33-16-12	ALL	
	Y	A016	BJ	W0148	028	22		33-16-12	ALL	
	Y	A016	BJ	W0148	029	22		33-16-12	ALL	
	Y	A016	BJ	W0148	030	22		33-16-12	ALL	
	Y	A016	BJ	W0148	031	22		33-16-12	ALL	
	Y	A017	BJ	W0154	009	22		33-16-12	ALL	
	Y	A017	BJ	W0154	010	22		33-16-12	ALL	
	Y	A017	BJ	W0154	011	22		33-16-12	ALL	
	Y	A017	BJ	W0154	018	22		33-16-12	ALL	
	Y	A018	BJ	W0152	011	22		33-16-12	ALL	
	Y	A018	BJ	W0152	013	22		33-16-12	ALL	
	Y	A018	BJ	W0152	014	22		33-16-12	ALL	
	Y	A019	BJ	W0158	017	22		33-16-12	ALL	
	Y	A019	BJ	W0158	018	22		33-16-12	ALL	
	Y	A019	BJ	W0158	021	22		33-16-12	ALL	
	Y	A019	BJ	W0158	105	22		33-16-12	ALL	
	Y	A020	BJ	W0156	048	22		33-16-12	ALL	
	Y	A020	BJ	W0156	049	22		33-16-12	ALL	
	Y	A020	BJ	W0156	050	22		33-16-12	ALL	
	Y	A021	BJ	W0156	054	22		33-16-12	ALL	
	Y	A021	BJ	W0156	055	22		33-16-12	ALL	
	Y	A021	BJ	W0156	056	22		33-16-12	ALL	

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 5

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0018		<b>BACT44A0460D (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P006-00/ /</b>		<b>ALL</b>
TB0018	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P006-00/ /</b>		<b>ALL</b>
	X	B001	BJ	W0148	060	24		33-16-11	ALL
	X	B001	BJ	W0152	009	24		33-16-11	ALL
	X	B002	BJ	W0148	037	22		33-16-12	ALL
	X	B002	BJ	W0154	006	22		33-16-12	ALL
	X	C001	BJ	W0152	046	24		80-11-11	ALL
	X	C001	BJ	W0158	083	24		80-11-11	ALL
	X	C002	BJ	W0148	062	24		33-16-11	ALL
	X	C002	BJ	W0156	037	22		33-16-11	ALL
	Y	C003	BJ	W0156	004	24		33-11-11	ALL
	Y	C003	BJ	W0156	006	24		33-11-11	ALL
	Y	C003	BJ	W0158	005	24		33-11-11	ALL
	Y	C004	BJ	W0158	003	24		33-11-11	ALL
	Y	C004	BJ	W0158	004	24		33-11-11	ALL
	Y	C004	BJ	W0158	006	24		33-11-11	ALL
	Y	C005	BJ	W0152	001	20		33-11-14	ALL
	Y	C005	BJ	W0156	017	20		33-11-14	ALL
	Y	C006	BJ	W0148	010	24		33-16-11	ALL
	Y	C006	BJ	W0152	007	24		33-16-11	ALL
	Y	C006	BJ	W0156	033	24		33-16-11	ALL
	Y	C006	BJ	W0156	042	24		33-16-11	ALL
	Y	C007	BJ	W0148	044	22		33-16-21	ALL
	Y	C007	BJ	W0152	029	22		33-16-21	ALL
	Y	C007	BJ	W0156	068	22		33-16-21	ALL
	Y	C007	BJ	W0158	101	22		33-16-21	ALL
	Y	C008	BJ	W0148	046	22		33-16-21	ALL
	Y	C008	BJ	W0152	032	22		33-16-21	ALL
	Y	C008	BJ	W0152	048	22		33-16-21	ALL
	Y	C008	BJ	W0156	073	22		33-16-21	ALL
	Y	C014	BJ	W0150	009	22		33-16-12	ALL
	Y	C014	BJ	W0150	010	22		33-16-12	ALL
	Y	C014	BJ	W0150	011	22		33-16-12	ALL
	Y	C014	BJ	W0150	012	22		33-16-12	ALL
	Y	C016	BJ	W0148	038	22		33-16-12	ALL
	Y	C016	BJ	W0154	004	22		33-16-12	ALL
	Y	C016	BJ	W0154	007	22		33-16-12	ALL
	Y	C017	BJ	W0154	012	22		33-16-12	150-154, 275-278

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 6

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0018		<b>BACT44A0460D (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0018	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P006-00/ /</b>		<b>ALL</b>
TB0018	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P006-00/ /</b>		<b>ALL</b>
	Y	C017	BJ	W0154	013	22		33-16-12	150-154, 275-278
	Y	C017	BJ	W0154	014	22		33-16-12	150-154, 275-278
	Y	C018	BJ	W0152	017	22		33-16-12	ALL
	Y	C018	BJ	W0152	018	22		33-16-12	ALL
	Y	C018	BJ	W0152	019	22		33-16-12	ALL
	Y	C019	BJ	W0156	044	22		33-16-12	ALL
	Y	C019	BJ	W0156	045	22		33-16-12	ALL
	Y	C019	BJ	W0156	047	22		33-16-12	ALL
	Y	C019	BJ	W0156	141	22		33-16-12	ALL
	Y	C020	BJ	W0156	051	22		33-16-12	ALL
	Y	C020	BJ	W0156	052	22		33-16-12	ALL
	Y	C020	BJ	W0156	053	22		33-16-12	ALL
	Y	C020	BJ	W0156	142	22		33-16-12	ALL
	Y	C021	BJ	W0156	057	22		33-16-12	ALL
	Y	C021	BJ	W0156	058	22		33-16-12	ALL
	Y	C021	BJ	W0156	059	22		33-16-12	ALL
	X	D001	BJ	W0152	047	24		80-11-21	ALL
	X	D001	BJ	W0156	148	24		80-11-21	ALL
	X	D002	BJ	W0148	008	24		33-16-11	ALL
	X	D002	BJ	W0156	165	24		33-16-11	ALL
	Y	DED		W0150	009Z			33-16-12	ALL
	Y	DED		W0150	010Z			33-16-12	ALL
	Y	DED		W0150	011Z			33-16-12	ALL
	Y	DED		W0150	012Z			33-16-12	ALL
	F	DED		W0150	023Z			33-13-18	ALL
	X	DED		W0152	046Z			80-11-11	ALL
	X	DED		W0152	047Z			80-11-21	ALL
	Y	DED		W0154	009Z			33-16-12	ALL
	Y	DED		W0154	010Z			33-16-12	ALL
	Y	DED		W0154	011Z			33-16-12	ALL
	Y	DED		W0154	012Z			33-16-12	150-154, 275-278
	Y	DED		W0154	013Z			33-16-12	150-154, 275-278
	Y	DED		W0154	014Z			33-16-12	150-154, 275-278
	Y	DED		W0154	018Z			33-16-12	ALL
	Y	DED		W0158	017Z			33-16-12	ALL
	Y	DED		W0158	018Z			33-16-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 7

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0018		BACT44A0460D (continued)					P006-05/ /		ALL
TB0018	F	BACM15C1A (continued)					P006-05/ /		ALL
TB0018	X	BACM15C3A (continued)					P006-05/ /		ALL
TB0018	Y	BACM15C3B (continued)					P006-00/ /		ALL
TB0018	Z	BACM15C3C (continued)					P006-00/ /		ALL
	Y	DED		W0158	021Z			33-16-12	ALL
	Y	DED		W0158	105Z			33-16-12	ALL
TB0022		BACT44A0460D					P006-05/ /		ALL
TB0022	D	DIODEBLOCK-REF284T0997-					P006-05/ /		ALL
TB0022	Y	BACM15C3B					P006-05/ /		ALL
TB0022	Z	BACM15C3C					P006-05/ /		ALL
	Z	21	BJ	W0156	107	24		80-11-21	ALL
	Z	21	BJ	W0156	110	20		80-11-21	ALL
	Z	21	BJ	W0156	111	20		80-11-21	ALL
	Z	21	BJ	W0156	112	24		80-11-21	ALL
	Z	21	BJ	W0156	149	24		80-11-21	ALL
	Z	22	BJ	W0158	045	24		80-11-11	ALL
	Z	22	BJ	W0158	051	20		80-11-11	ALL
	Z	22	BJ	W0158	052	20		80-11-11	ALL
	Z	22	BJ	W0158	054	24		80-11-11	ALL
	Z	22	BJ	W0158	084	24		80-11-11	ALL
	D	A001	2	W0148	059	24		80-11-11	ALL
	D	A002	2	W0152	044	24		80-11-21	ALL
	Y	A003	BJ	W0158	036	24		80-11-11	ALL
	Y	A003	BJ	W0158	041	24		80-11-11	ALL
	Y	A003	BJ	W0158	042	24		80-11-11	ALL
	Y	A004	BJ	W0158	043	20		80-11-11	ALL
	Y	A004	BJ	W0158	044	20		80-11-11	ALL
	Y	A004	BJ	W0158	050	24		80-11-11	ALL
	Y	A005	BJ	W0156	108	24		80-11-21	ALL
	Y	A005	BJ	W0158	046	22		80-11-11	ALL
	Y	A005	BJ	W0158	047	24		80-11-11	ALL
	Y	A006	BJ	W0156	100	20		80-11-21	ALL
	Y	A006	BJ	W0156	101	20		80-11-21	ALL
	Y	A006	BJ	W0156	102	24		80-11-21	ALL
	Y	A007	BJ	W0156	105	20		80-11-21	ALL
	Y	A007	BJ	W0156	106	20		80-11-21	ALL
	Y	A007	BJ	W0156	113	24		80-11-21	ALL
	Y	A008	BJ	W0150	020	24		24-51-71	ALL
	Y	A008	BJ	W0156	134	24		24-51-71	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 8

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0022		<b>BACT44A0460D (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0022	<b>D</b>	<b>DIODEBLOCK-REF284T0997- (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0022	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0022	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
	Y	A008	BJ	W0158	076	24		24-51-71	ALL
	D	A013	2	W0148	058	24		80-11-11	ALL
	D	A013	2	W0148	059	24		80-11-11	ALL
	D	A014	2	W0152	043	24		80-11-21	ALL
	D	A014	2	W0152	044	24		80-11-21	ALL
	Y	A015	BJ	W0158	030	24		80-11-11	ALL
	Y	A015	BJ	W0158	037	24		80-11-11	ALL
	Y	A015	BJ	W0158	080	24		80-11-11	ALL
	Y	A018	BJ	W0158	007	24		33-11-11	ALL
	Y	A018	BJ	W0158	110	24		33-11-11	ALL
	Y	A018	BJ	W0158	116	24		33-11-11	ALL
	Y	A020	BJ	W0158	031	24		80-11-11	ALL
	Y	A020	BJ	W0158	033	24		80-11-11	ALL
	Y	A020	BJ	W0158	034	24		80-11-11	ALL
	D	C001	2	W0158	080	24		80-11-11	ALL
	D	C002	2	W0156	138	24		80-11-21	ALL
	Y	C003	BJ	W0156	115	24		80-11-21	ALL
	Y	C003	BJ	W0158	049	22		80-11-11	ALL
	Y	C003	BJ	W0158	053	24		80-11-11	ALL
	Y	C005	BJ	W0156	093	24		80-11-21	ALL
	Y	C005	BJ	W0156	095	24		80-11-21	ALL
	Y	C005	BJ	W0156	096	24		80-11-21	ALL
	Y	C006	BJ	W0156	098	24		80-11-21	ALL
	Y	C006	BJ	W0156	103	24		80-11-21	ALL
	Y	C006	BJ	W0156	104	24		80-11-21	ALL
	Y	C008	BJ	W0150	021	24		24-51-71	ALL
	Y	C008	BJ	W0156	135	24		24-51-71	ALL
	Y	C008	BJ	W0158	077	24		24-51-71	ALL
	D	C013	2	W0158	117	24		80-11-11	ALL
	D	C014	2	W0156	171	24		80-11-21	ALL
	Y	C015	BJ	W0156	092	24		80-11-21	ALL
	Y	C015	BJ	W0156	099	24		80-11-21	ALL
	Y	C015	BJ	W0156	138	24		80-11-21	ALL
	Y	C018	BJ	W0156	008	24		33-11-11	ALL
	Y	C018	BJ	W0156	150	24		33-11-11	ALL
	Y	C018	BJ	W0156	164	24		33-11-11	ALL
	Y	C020	BJ	W0158	038	20		80-11-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 9

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0022		<b>BACT44A0460D (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0022	<b>D</b>	<b>DIODEBLOCK-REF284T0997- (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0022	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
TB0022	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P006-05/ /</b>		<b>ALL</b>
	Y	C020	BJ	W0158	039	20		80-11-11	ALL
	Y	C020	BJ	W0158	040	24		80-11-11	ALL
	Y	DED		W0150	020Z			24-51-71	ALL
	Y	DED		W0150	021Z			24-51-71	ALL
TB0024		<b>284T0914-1</b>					<b>P034-00/ /</b>		<b>ALL</b>
TB0024	<b>D</b>	<b>DIODEBLOCK-REF284T0175-</b>					<b>P034-00/ /</b>		<b>ALL</b>
TB0024	<b>F</b>	<b>BACM15C1A</b>					<b>P034-00/ /</b>		<b>ALL</b>
TB0024	<b>G</b>	<b>BACM15C1B</b>					<b>P034-00/ /</b>		<b>ALL</b>
TB0024	<b>R</b>	<b>RESISTORBLOCK-REF284T0175-</b>					<b>P034-00/ /</b>		<b>ALL</b>
	G	10	2	W0026	100	24		24-27-41	ALL
	G	10	2	W0026	101	24		24-27-41	ALL
	G	10	2	W0026	102	24		24-27-41	ALL
	G	11	2	W0026	103	24		24-27-41	ALL
	G	11	2	W0026	104	24		24-27-41	ALL
	G	11	2	W0026	105	24		24-27-41	ALL
	G	12	2	W0054	018	24		52-34-12	ALL
	G	12	2	W0054	054	24		52-34-12	ALL
	G	12	2	W0054	055	24		52-34-12	ALL
	G	12	2	W0054	056	24		52-35-12	ALL
	G	17	2	W0026	012	22		49-61-11	ALL
	G	17	2	W0026	051	22		49-61-11	ALL
	G	17	2	W0054	093	24		31-31-22	ALL
	D	A001	2	W0026	045	20		24-22-41	ALL
	R	A002	2	W0026	082	24		24-41-11	ALL
	F	A003	2	W0026	058	16		24-41-11	ALL
	F	A003	2	W0054	036	16		24-41-11	ALL
	F	A004	2	W0026	057	16		24-41-11	ALL
	F	A004	2	W0054	037	16		24-41-11	ALL
	F	A005	2	W0026	056	16		24-41-11	ALL
	F	A005	2	W0054	038	16		24-41-11	ALL
	F	A006	2	W0026	015	24		24-28-11	ALL
	F	A006	2	W0054	028	24		24-28-11	ALL
	F	A007	2	W0026	026	18		33-31-31	ALL
	F	A007	2	W0054	035	18		33-31-31	ALL
	F	A008	2	W0026	016	24		24-28-11	ALL
	F	A008	2	W0054	029	24		24-28-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 10

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0024		284T0914-1 (continued)					P034-00/ /		ALL
TB0024	D	DIODEBLOCK-REF284T0175- (continued)					P034-00/ /		ALL
TB0024	F	BACM15C1A (continued)					P034-00/ /		ALL
TB0024	G	BACM15C1B (continued)					P034-00/ /		ALL
TB0024	R	RESISTORBLOCK-REF284T0175- (continued)					P034-00/ /		ALL
	F	A009	2	W0026	108	24		24-51-71	ALL
	F	A009	2	W0026	110	24		24-51-71	ALL
	D	A013	2	W0026	097	22		49-61-11	ALL
	D	A013	2	W0026	098	24		49-61-11	ALL
	D	A014	2	W0026	098	24		49-61-11	ALL
	D	A015	2	W0054	058	22		73-21-19	ALL
	D	A016	2	W0054	060	22		73-21-19	ALL
	D	C001	2	W0026	029	20		24-22-41	ALL
	R	C002	2	W0026	083	24		24-41-11	ALL
	R	C002	2	W0026	084	24		24-41-11	ALL
	F	C003	2	W0026	039	24		24-41-11	ALL
	F	C003	2	W0054	030	22		24-41-11	ALL
	F	C004	2	W0026	038	24		24-41-11	ALL
	F	C004	2	W0054	032	22		24-41-11	ALL
	F	C005	2	W0026	037	24		24-41-11	ALL
	F	C005	2	W0054	033	22		24-41-11	ALL
	F	C006	2	W0026	027	18		24-28-11	ALL
	F	C006	2	W0054	034	18		24-28-11	ALL
	F	C007	2	W0026	032	24		24-51-61	ALL
	F	C007	2	W0054	042	24		24-51-61	ALL
	D	C013	2	W0026	064	22		49-61-11	ALL
	D	C014	2	W0026	107	24		28-25-21	ALL
	D	C015	2	W0054	059	22		73-21-19	ALL
	D	C016	2	W0054	061	22		73-21-19	ALL
TB0026		AMY4100T-10					SHELF/E06/01		ALL
TB0026	D	DIODEBLOCK-REF284T0161-					SHELF/E06/01		150-157
TB0026	F	BACM15C1A					SHELF/E06/01		ALL
TB0026	G	BACM15C1B					SHELF/E06/01		ALL
TB0026	H	BACM15C2A					SHELF/E06/01		ALL
TB0026	R	RESISTORBLOCK-REF284T0161-					SHELF/E06/01		ALL
	G	1	2	W0020	044	24		24-31-41	ALL
	G	1	2	W1038	012	24		24-31-41	ALL
	G	1	2	W1038	014	24		24-31-41	ALL
	G	3	2	W0020	029	22		49-61-11	ALL
	G	3	2	W0020	033	22		49-61-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 11

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0026		<b>AMY4100T-10 (continued)</b>					<b>SHELF/E06/01</b>		<b>ALL</b>
TB0026	<b>D</b>	<b>DIODEBLOCK-REF284T0161- (continued)</b>					<b>SHELF/E06/01</b>		<b>150-157</b>
TB0026	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E06/01</b>		<b>ALL</b>
TB0026	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E06/01</b>		<b>ALL</b>
TB0026	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E06/01</b>		<b>ALL</b>
TB0026	<b>R</b>	<b>RESISTORBLOCK-REF284T0161- (continued)</b>					<b>SHELF/E06/01</b>		<b>ALL</b>
	G	3	2	W0020	052	22		49-61-11	ALL
	G	6	2	W0020	030	24		36-11-41	150-157
	G	6	2	W0020	071	24		24-27-41	150-157
	G	6	2	W1038	019	24		36-11-41	150-157
	F	A004	2	W0020	054	24		36-11-41	ALL
	F	A004	2	W1038	021	24		36-11-41	ALL
	F	A005	2	W0020	056	20		36-11-41	ALL
	F	A005	2	W1038	018	20		36-11-41	ALL
	D	A032	2	W0020	070	24		24-27-41	150-157
	F	C002	2	W0020	031	24		36-11-41	ALL
	F	C002	2	W1038	020	24		36-11-41	ALL
	F	C004	2	W0020	055	20		36-11-41	ALL
	F	C004	2	W1038	017	20		36-11-41	ALL
	F	C005	2	W0020	057	24		36-11-41	ALL
	F	C005	2	W1038	022	24		36-11-41	ALL
	D	C032	2	W0020	071	24		24-27-41	150-157
<b>TB0028</b>		<b>BACT44A0640D</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0028</b>	<b>D</b>	<b>DIDOEBLOCK-REF284T0189-</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0028</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0028</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0028</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P031-00/ /</b>		<b>150-199, 275-299</b>
	G	1	2	W0022	040	20		25-31-21	150-199
	G	1	2	W0022	040	18		25-31-21	275-278
	G	1	2	W0022	042	20		25-31-21	150-199
	G	1	2	W0022	042	18		25-31-21	275-278
	G	1	2	W0022	153	18		25-31-31	275-276
	G	11	2	W0022	130	24		24-51-71	ALL
	G	11	2	W0022	134	24		24-51-71	ALL
	G	11	2	W0022	135	24		24-51-71	ALL
	G	12	2	W0022	131	24		24-51-71	ALL
	G	12	2	W0022	132	24		24-51-71	ALL
	G	12	2	W0022	133	24		24-51-71	ALL
	G	2	2	W0022	017	24		24-27-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 12

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0028</b>		<b>BACT44A0640D (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0028</b>	<b>D</b>	<b>DIDOBLOCK-REF284T0189- (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0028</b>	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0028</b>	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0028</b>	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P031-00/ /</b>		<b>150-199, 275-299</b>
	G	2	2	W0022	018	24		24-27-11	ALL
	G	2	2	W0022	019	24		24-27-11	ALL
	G	3	2	W0022	023	24		24-27-21	ALL
	G	3	2	W0022	025	24		24-27-21	ALL
	G	3	2	W0022	026	24		24-27-21	ALL
	G	4	2	W0022	024	24		24-27-21	ALL
	G	4	2	W0022	027	24		24-27-21	ALL
	G	4	2	W0022	029	24		24-27-21	ALL
	D	A006	2	W0022	005	20		24-22-11	ALL
	D	A007	2	W0022	051	20		24-22-12	ALL
	D	A008	2	W0022	123	24		24-51-31	ALL
	F	A009	2	W0022	060	18		24-21-11	ALL
	F	A009	2	W1016	013	18		24-21-11	ALL
	F	A010	2	W0022	062	18		24-21-11	ALL
	F	A010	2	W1016	015	18		24-21-11	ALL
	D	C006	2	W0022	007	20		24-22-11	ALL
	D	C007	2	W0022	050	20		24-22-12	ALL
	D	C008	2	W0022	124	24		24-51-31	ALL
	F	C009	2	W0022	061	18		24-21-11	ALL
	F	C009	2	W1016	014	18		24-21-11	ALL
	Y	C013	BJ	W0022	044	22		25-31-21	150-199, 275-299
	Y	C013	BJ	W0022	171	22		25-31-21	150-199, 275-299
	Y	C013	BJ	W0022	179	22		25-31-31	275-299
<b>TB0030</b>		<b>BACT44A0460D</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0030</b>	<b>D</b>	<b>DIODEBLOCK-REF284T0171-</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0030</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0030</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P031-00/ /</b>		<b>ALL</b>
<b>TB0030</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P031-00/ /</b>		<b>ALL</b>
	G	10	2	W0022	092	24		24-51-31	150-199, 275-299
	G	10	2	W0022	093	24		24-51-31	150-199, 275-299
	G	10	2	W0022	094	24		24-51-31	150-199, 275-299
	G	10	2	W0022	095	24		24-51-31	150-199, 275-299
	G	11	2	W0022	098	20		24-22-12	150-199, 275-299
	G	11	2	W0022	099	20		24-22-12	150-199, 275-299
	G	11	2	W0022	100	20		24-22-12	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 13

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0030		<b>BACT44A0460D (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
TB0030	<b>D</b>	<b>DIODEBLOCK-REF284T0171- (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
TB0030	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
TB0030	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
TB0030	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
	G	12	2	W0022	021	24		24-27-11	150-199, 275-299
	G	12	2	W0022	138	24		24-27-11	150-199, 275-299
	G	12	2	W0022	139	24		24-27-11	150-199, 275-299
	G	2	2	W0022	022	24		24-27-11	ALL
	G	2	2	W0022	136	24		24-27-11	ALL
	G	2	2	W0022	137	24		24-27-11	ALL
	G	7	2	W0022	110	24		29-11-31	ALL
	G	7	2	W0022	112	24		29-11-31	ALL
	G	7	2	W0022	115	24		29-11-31	ALL
	G	7	2	W0022	117	24		29-11-31	ALL
	G	8	2	W0022	054	20		24-22-12	ALL
	G	8	2	W0022	087	20		24-22-12	ALL
	G	8	2	W0022	088	20		24-22-12	ALL
	F	A001	2	W0022	077	22		29-32-11	ALL
	F	A001	2	W0288	011	18		29-32-11	ALL
	Y	A003	BJ	W0022	108	22		29-11-31	ALL
	Y	A003	BJ	W0022	109	24		29-11-31	ALL
	Y	A003	BJ	W0022	111	24		29-11-31	ALL
	Y	A003	BJ	W0022	113	24		29-11-31	ALL
	Y	A004	BJ	W0022	072	24		29-11-22	ALL
	Y	A004	BJ	W0022	073	24		29-11-22	ALL
	Y	A004	BJ	W0022	074	24		29-11-22	ALL
	Y	A005	BJ	W0022	075	24		29-11-22	ALL
	Y	A005	BJ	W0022	083	24		29-11-22	ALL
	Y	A005	BJ	W0022	145	24		29-11-22	ALL
	Y	A006	BJ	W0022	076	24		29-11-22	ALL
	Y	A006	BJ	W0022	128	24		29-11-22	ALL
	Y	A006	BJ	W0022	129	24		31-31-26	ALL
	Y	A011	BJ	W0022	092	24		24-51-31	050-099
	Y	A011	BJ	W0022	093	24		24-51-31	050-099
	Y	A011	BJ	W0022	094	24		24-51-31	050-099
	Y	A011	BJ	W0022	095	24		24-51-31	050-099
	Y	A012	BJ	W0022	021	24		24-27-11	050-099
	Y	A012	BJ	W0022	138	24		24-27-11	050-099
	Y	A012	BJ	W0022	139	24		24-27-11	050-099
	Y	C003	BJ	W0022	064	22		29-11-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 14

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0030		<b>BACT44A0460D (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
TB0030	<b>D</b>	<b>DIODEBLOCK-REF284T0171- (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
TB0030	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
TB0030	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
TB0030	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P031-00/ /</b>		<b>ALL</b>
	Y	C003	BJ	W0022	065	22		29-11-31	ALL
	Y	C003	BJ	W0022	066	22		29-11-31	ALL
	Y	C004	BJ	W0022	107	24		29-11-31	ALL
	Y	C004	BJ	W0022	114	24		29-11-31	ALL
	Y	C004	BJ	W0022	116	24		29-11-31	ALL
	Y	C004	BJ	W0022	118	24		29-11-31	ALL
	Y	C005	BJ	W0022	067	24		29-11-31	ALL
	Y	C005	BJ	W0022	085	24		29-11-31	ALL
	Y	C005	BJ	W0022	147	24		29-11-31	ALL
	Y	C006	BJ	W0022	089	24		24-51-31	ALL
	Y	C006	BJ	W0022	090	24		24-51-31	ALL
	Y	C006	BJ	W0022	091	24		24-51-31	ALL
	Y	C011	BJ	W0022	098	20		24-22-12	050-099
	Y	C011	BJ	W0022	099	20		24-22-12	050-099
	Y	C011	BJ	W0022	100	20		24-22-12	050-099
TB0031		<b>BACT44A0920D</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	<b>F</b>	<b>BACM15C1A</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	<b>G</b>	<b>BACM15C1B</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	<b>H</b>	<b>BACM15C2A</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	<b>Y</b>	<b>BACM15C3B</b>					<b>0212/195/L045</b>		<b>ALL</b>
	G	10	2	W0614	174	22		33-16-18	ALL
	G	10	2	W0634	134	22		33-16-12	ALL
	H	11	2	W0262	037	22		33-16-18	ALL
	H	11	2	W0264	054	22		33-16-18	ALL
	H	11	2	W0264	056	22		33-16-18	ALL
	H	11	2	W0634	136	22		33-16-12	ALL
	H	13	2	W0606	552	22		33-16-18	ALL
	H	13	2	W0614	175	22		33-16-18	ALL
	H	13	2	W0614	555	22		33-16-18	ALL
	H	13	2	W0634	137	22		33-16-12	ALL
	G	15	2	W0606	555	22		33-16-18	ALL
	G	15	2	W0614	552	22		33-16-18	ALL
	G	15	2	W0634	138	22		33-16-12	ALL
	H	16	2	W0262	036	22		33-16-18	ALL
	H	16	2	W0264	053	22		33-16-18	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 15

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0031		<b>BACT44A0920D (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	F	<b>BACM15C1A (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	G	<b>BACM15C1B (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	H	<b>BACM15C2A (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	Y	<b>BACM15C3B (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
	H	16	2	W0606	553	22		33-16-18	ALL
	H	16	2	W0606	554	22		33-16-18	ALL
	H	16	2	W0606	560	22		33-16-18	ALL
	H	16	2	W0614	551	22		33-16-18	ALL
	H	16	2	W0634	172	22		33-16-12	ALL
	H	18	2	W0264	055	22		33-16-18	ALL
	H	18	2	W0606	551	22		33-16-18	ALL
	H	18	2	W0614	553	22		33-16-18	ALL
	H	18	2	W0614	554	22		33-16-18	ALL
	H	18	2	W0634	177	22		33-16-12	ALL
	G	27	2	W0638	158	22		33-16-12	150-154, 275-278
	G	27	2	W0687	018	22		33-16-18	150-154, 275-278
	H	6	2	W0632	117	22		33-16-12	ALL
	H	6	2	W0685	021	22		33-16-18	ALL
	H	6	2	W0847	017	22		SPARE	167-199
	H	6	2	W0851	045	22		33-16-18	275-299
	H	6	2	W0851	906	22		23-22-12	150, 152-199
	H	8	2	W0632	157	22		33-16-12	ALL
	H	8	2	W0685	018	22		33-16-18	ALL
	H	8	2	W0847	016	22		SPARE	167-199
	H	8	2	W0851	046	22		33-16-18	275-299
	H	8	2	W0851	901	22		23-22-12	150, 152-199
	Y	A003	BJ	W0481	062	24		31-51-33	ALL
	Y	A003	BJ	W0606	562	24		31-51-33	ALL
	Y	A003	BJ	W0606	631	24		25-33-11	050-099, 150-199, 277-299
	Y	A003	BJ	W0606	631	24		21-58-16	275-276
	Y	A004	BJ	W0517	027	22		33-16-18	ALL
	Y	A004	BJ	W0634	143	22		33-16-18	ALL
	F	A022	2	W0481	047	20		27-21-11	ALL
	F	A022	2	W0756	143	20		27-21-11	ALL
	F	A023	2	W0481	060	22		31-51-33	ALL
	F	A023	2	W0606	549	24		31-51-33	ALL
	F	A025	2	W0634	083	22		33-16-17	ALL
	F	A025	2	W0723	028	22		33-16-17	ALL
	F	A026	2	W0632	063	22		33-16-17	ALL
	F	A026	2	W0751	028	22		33-16-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 16

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0031		<b>BACT44A0920D (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	F	<b>BACM15C1A (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	G	<b>BACM15C1B (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	H	<b>BACM15C2A (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
TB0031	Y	<b>BACM15C3B (continued)</b>					<b>0212/195/L045</b>		<b>ALL</b>
	Y	C003	BJ	W0481	061	24		31-51-33	ALL
	Y	C003	BJ	W0614	562	24		31-51-33	ALL
	Y	C003	BJ	W0614	631	24		25-33-11	050-099, 150-199, 277-299
	Y	C003	BJ	W0614	631	24		21-58-16	275-276
	Y	C004	BJ	W0517	023	22		33-16-18	ALL
	Y	C004	BJ	W0634	144	22		33-16-18	ALL
	F	C024	2	W0614	549	24		31-51-33	ALL
	F	C024	2	W0685	015	24		31-51-33	ALL
	F	C025	2	W0638	063	22		33-16-17	ALL
	F	C025	2	W0725	028	22		33-16-17	ALL
	F	C026	2	W0606	550	24		31-51-33	ALL
	F	C026	2	W0687	001	24		31-51-33	ALL
	H	DED		W0632	157Z			33-16-12	ALL
	H	DED		W0634	172Z			33-16-12	ALL
	H	DED		W0634	177Z			33-16-12	ALL
	G	DED		W0638	158Z			33-16-12	150-154, 275-278
	F	DED		W0756	143Z			27-21-11	ALL
TB0032		<b>BACT44A0460D</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0032	D	<b>DIODEBLOCK-REF284T0172-</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0032	F	<b>BACM15C1A</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0032	G	<b>BACM15C1B</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0032	Y	<b>BACM15C3B</b>					<b>P032-00/ /</b>		<b>ALL</b>
	G	10	2	W0024	120	24		29-11-31	ALL
	G	10	2	W0024	159	24		29-11-31	ALL
	G	10	2	W0024	160	24		29-11-31	ALL
	G	5	2	W0024	031	24		24-27-21	ALL
	G	5	2	W0024	032	24		24-27-21	ALL
	G	5	2	W0024	033	24		24-27-21	ALL
	G	9	2	W0024	180	18		30-71-25	050-099, 150-199
	G	9	2	W0024	181	18		30-71-25	050-099, 150-199
	G	9	2	W0024	182	18		30-71-25	050-099, 150-199
	G	9	2	W0024	183	18		30-71-25	050-099, 150-199
	F	A001	2	W0024	034	24		24-27-21	ALL
	F	A001	2	W0024	035	24		24-27-21	ALL
	F	A002	2	W0024	060	22		29-32-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 17

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0032		<b>BACT44A0460D (continued)</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0032	<b>D</b>	<b>DIODEBLOCK-REF284T0172- (continued)</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0032	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0032	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0032	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P032-00/ /</b>		<b>ALL</b>
	F	A002	2	W0290	012	20		29-32-11	ALL
	Y	A003	BJ	W0024	021	24		24-27-11	ALL
	Y	A003	BJ	W0024	023	24		24-27-11	ALL
	Y	A003	BJ	W0024	024	24		24-27-11	ALL
	Y	A004	BJ	W0024	040	24		29-11-12	ALL
	Y	A004	BJ	W0024	069	24		29-11-12	ALL
	Y	A004	BJ	W0024	157	24		29-11-12	ALL
	D	A006	2	W0024	009	20		24-22-21	ALL
	D	A007	2	W0024	016	20		24-22-22	ALL
	D	A008	2	W0024	134	24		24-51-31	ALL
	Y	A011	BJ	W0024	064	24		29-11-12	ALL
	Y	A011	BJ	W0024	065	24		29-11-12	ALL
	Y	A011	BJ	W0024	066	24		29-11-12	ALL
	Y	A012	BJ	W0024	028	24		24-27-21	ALL
	Y	A012	BJ	W0024	147	24		24-27-21	ALL
	Y	A012	BJ	W0024	148	24		24-27-21	ALL
	Y	C003	BJ	W0024	025	24		24-27-11	ALL
	Y	C003	BJ	W0024	026	24		24-27-11	ALL
	Y	C003	BJ	W0024	027	24		24-27-11	ALL
	Y	C004	BJ	W0024	057	24		29-11-31	ALL
	Y	C004	BJ	W0024	068	24		29-11-31	ALL
	Y	C004	BJ	W0024	161	24		29-11-31	ALL
	D	C006	2	W0024	010	20		24-22-21	ALL
	D	C007	2	W0024	017	20		24-22-22	ALL
	D	C008	2	W0024	135	24		24-51-31	ALL
	Y	C011	BJ	W0024	030	24		24-27-21	ALL
	Y	C011	BJ	W0024	149	24		24-27-21	ALL
	Y	C011	BJ	W0024	150	24		24-27-21	ALL
	Y	C012	BJ	W0024	054	24		29-11-31	ALL
	Y	C012	BJ	W0024	055	24		29-11-31	ALL
	Y	C012	BJ	W0024	056	24		29-11-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 18

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0034		<b>BACT44A0460D</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0034	<b>F</b>	<b>BACM15C1A</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0034	<b>G</b>	<b>BACM15C1B</b>					<b>P032-00/ /</b>		<b>ALL</b>
TB0034	<b>R</b>	<b>RESISTORBLOCK</b>					<b>P032-00/ /</b>		<b>050-099, 150-157</b>
	G	1	2	W0024	078	20		25-31-11	155-199
	G	1	2	W0024	079	20		25-31-11	155-199
	G	1	2	W0024	156	20		25-31-12	155-199
	G	11	2	W0024	123	24		29-11-31	ALL
	G	11	2	W0024	124	24		29-11-31	ALL
	G	11	2	W0024	125	24		29-11-31	ALL
	G	2	2	W0024	081	22		25-31-11	280-299
	G	2	2	W0024	084	22		25-31-11	050-099, 150-199, 280-299
	G	2	2	W0024	151	22		25-31-11	050-099, 150-199
	G	2	2	W0024	165	22		25-31-12	050-099, 150-199
	G	3	2	W0024	070	24		29-11-12	ALL
	G	3	2	W0024	176	24		29-11-12	ALL
	G	3	2	W0024	177	24		31-31-26	ALL
	G	5	2	W0024	099	24		24-22-12	ALL
	G	5	2	W0024	100	24		24-22-12	ALL
	G	5	2	W0024	101	24		24-22-12	ALL
	G	6	2	W0024	107	24		24-51-31	ALL
	G	6	2	W0024	108	24		24-51-31	ALL
	G	6	2	W0024	116	24		24-51-31	ALL
	G	7	2	W0024	019	20		24-22-22	ALL
	G	7	2	W0024	109	20		24-22-22	ALL
	G	7	2	W0024	117	20		24-22-22	ALL
	G	8	2	W0024	110	20		24-22-22	ALL
	G	8	2	W0024	115	20		24-22-22	ALL
	G	8	2	W0024	119	20		24-22-22	ALL
	G	9	2	W0024	111	24		24-51-31	ALL
	G	9	2	W0024	113	24		24-51-31	ALL
	G	9	2	W0024	114	24		24-51-31	ALL
	G	9	2	W0024	118	24		24-51-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 19

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0064		BACT44B0780D					0191/279/R012		ALL
TB0064	D	DIODEBLOCK-REF233T3100-					0202/280/R008		ALL
TB0064	F	BACM15C1A					0200/275/R010		050-099, 156-157, 166-199, 277-299
TB0064	G	BACM15C1B					0202/267/R010		ALL
TB0064	X	BACM15C3A					P005-00/ /		ALL
TB0064	Y	BACM15C3B					P005-00/ /		ALL
TB0064	Z	BACM15C3C					P005-00/ /		ALL
	G	1	2	W0062	10B	16		33-13-16	ALL
	G	1	2	W0627	011	20		33-13-16	ALL
	G	1	2	W0675	001	20		33-13-16	ALL
	Z	12	BJ	W0062	09M	22		33-13-16	ALL
	Z	12	BJ	W0062	10A	22		33-13-16	ALL
	Z	12	BJ	W0062	10M	22		33-13-16	ALL
	Z	12	BJ	W0062	10T	22		33-13-16	ALL
	Z	12	BJ	W0062	11M	22		33-13-16	ALL
	Z	13	BJ	W0062	303R	24		33-13-16	ALL
	Z	13	BJ	W0062	307R	24		33-13-16	ALL
	Z	13	BJ	W0062	308R	24		33-13-16	ALL
	Z	13	BJ	W0062	309R	24		33-13-16	ALL
	Z	13	BJ	W0062	311R	24		33-13-16	ALL
	Z	13	BJ	W0062	315R	24		33-13-16	ALL
	Z	14	BJ	W0062	303B	24		33-13-16	ALL
	Z	14	BJ	W0062	307B	24		33-13-16	ALL
	Z	14	BJ	W0062	308B	24		33-13-16	ALL
	Z	14	BJ	W0062	309B	24		33-13-16	ALL
	Z	14	BJ	W0062	311B	24		33-13-16	ALL
	Z	14	BJ	W0062	315B	24		33-13-16	ALL
	Z	15	BJ	W0062	303Y	24		33-13-16	ALL
	Z	15	BJ	W0062	307Y	24		33-13-16	ALL
	Z	15	BJ	W0062	308Y	24		33-13-16	ALL
	Z	15	BJ	W0062	309Y	24		33-13-16	ALL
	Z	15	BJ	W0062	311Y	24		33-13-16	ALL
	Z	15	BJ	W0062	315Y	24		33-13-16	ALL
	G	2	2	W0062	12S	22		33-13-16	ALL
	G	2	2	W0070	611	20		33-13-16	ALL
	G	2	2	W0070	631	20		33-13-16	ALL
	G	3	2	W0062	10J	16		33-13-16	ALL
	G	3	2	W0062	721	18		33-13-16	ALL
	G	3	2	W0066	581	20		33-13-16	ALL
	G	3	2	W0863	043	20		33-13-16	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 20

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0064		<b>BACT44B0780D (continued)</b>					<b>0191/279/R012</b>		<b>ALL</b>
TB0064	<b>D</b>	<b>DIODEBLOCK-REF233T3100- (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0064	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>0200/275/R010</b>		<b>050-099, 156-157, 166-199, 277-299</b>
TB0064	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>0202/267/R010</b>		<b>ALL</b>
TB0064	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0064	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0064	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	G	4	2	W0062	12V	16		33-13-16	ALL
	G	4	2	W0062	530	20		33-13-16	050-099, 155-199, 276-299
	G	4	2	W0066	131	20		33-13-16	ALL
	G	4	2	W0066	601	18		33-13-16	ALL
	G	5	2	W0062	041	18		33-13-16	ALL
	G	5	2	W0062	12J	16		33-13-16	ALL
	G	5	2	W0062	12M	22		33-13-16	ALL
	G	5	2	W0070	061	18		33-13-16	ALL
	G	6	2	W0062	526	20		33-13-16	050-099, 155-199, 276-299
	G	6	2	W0062	530	20		33-13-16	050-099, 155-199, 276-299
	G	6	2	W0066	509	20		33-13-16	050-099, 155-199, 276-299
	G	7	2	W0062	13J	16		33-13-16	ALL
	G	7	2	W0062	701	18		33-13-16	ALL
	G	7	2	W0066	03A	20		33-13-16	ALL
	G	8	2	W0062	03A	20		33-13-16	ALL
	G	8	2	W0062	13H	16		33-13-16	ALL
	G	8	2	W0066	175	20		33-13-16	ALL
	D	A010	2	W0066	081	24		36-11-41	ALL
	F	A011	2	W0675	018	24		23-25-14	156-157, 166-199, 277-278
	F	A011	2	W0683	017	24		23-25-14	156-157, 166-199, 277-299
	F	A016	2	W0675	020	24		23-25-14	156-157, 166-199, 277-278
	F	A016	2	W0683	019	24		23-25-14	156-157, 166-199, 277-299
	X	A017	BJ	W0060	005	22		49-61-11	ALL
	X	A017	BJ	W0070	695	22		49-61-11	ALL
	X	A018	BJ	W0062	12T	22		33-13-16	ALL
	X	A018	BJ	W0070	12Z	22		33-13-16	ALL
	D	C010	2	W0060	022	24		36-11-41	ALL
	D	C010	2	W0066	646	24		36-11-41	ALL
	F	C011	2	W0675	019	24		23-25-14	156-157, 166-199, 277-278
	F	C011	2	W0683	018	24		23-25-14	156-157, 166-199, 277-299
	Y	C019	BJ	W0062	12P	24		33-13-16	ALL
	Y	C019	BJ	W0062	12X	24		33-13-16	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 21

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0064		<b>BACT44B0780D (continued)</b>					<b>0191/279/R012</b>		<b>ALL</b>
TB0064	<b>D</b>	<b>DIODEBLOCK-REF233T3100- (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0064	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>0200/275/R010</b>		<b>050-099, 156-157, 166-199, 277-299</b>
TB0064	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>0202/267/R010</b>		<b>ALL</b>
TB0064	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0064	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0064	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	<b>Y</b>	C019	BJ	W0062	66S	24		33-13-16	ALL
	<b>X</b>	DED		W0062	12TZ			33-13-16	ALL
	<b>X</b>	DED		W0070	695Z			49-61-11	ALL
	<b>F</b>	DED		W0675	018Z			23-25-14	156-157, 166-199, 277-278
	<b>F</b>	DED		W0675	019Z			23-25-14	156-157, 166-199, 277-278
	<b>F</b>	DED		W0675	020Z			23-25-14	156-157, 166-199, 277-278
TB0066		<b>BACT44B1180D</b>					<b>0191/280/R008</b>		<b>ALL</b>
TB0066	<b>X</b>	<b>BACM15C3A</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	<b>Y</b>	<b>BACM15C3B</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	<b>Z</b>	<b>BACM15C3C</b>					<b>0202/280/R008</b>		<b>ALL</b>
	<b>Z</b>	23	BJ	W0070	01H	24		21-58-11	ALL
	<b>Z</b>	23	BJ	W0723	021	24		21-58-11	ALL
	<b>Z</b>	23	BJ	W0725	021	24		21-58-11	ALL
	<b>Z</b>	23	BJ	W0751	021	24		21-58-11	ALL
	<b>Z</b>	23	BJ	W0863	006	24		21-58-11	ALL
	<b>Z</b>	27	BJ	W0066	003	22		33-16-17	ALL
	<b>Z</b>	27	BJ	W0066	073	22		33-16-17	ALL
	<b>Z</b>	27	BJ	W0066	525	22		33-16-17	050-099, 155-199, 276-299
	<b>Z</b>	27	BJ	W0066	603	22		33-16-17	ALL
	<b>Z</b>	27	BJ	W0066	60L	22		33-16-22	ALL
	<b>Z</b>	27	BJ	W0066	651	22		33-16-17	ALL
	<b>Z</b>	28	BJ	W0066	01D	22		33-16-17	ALL
	<b>Z</b>	28	BJ	W0066	134	22		33-16-17	ALL
	<b>Z</b>	28	BJ	W0066	504	22		33-16-17	ALL
	<b>Z</b>	28	BJ	W0066	60W	22		33-16-22	ALL
	<b>Z</b>	29	BJ	W0066	004	22		33-16-17	ALL
	<b>Z</b>	29	BJ	W0066	074	22		33-16-17	ALL
	<b>Z</b>	29	BJ	W0066	526	22		33-16-17	050-099, 155-199, 276-299
	<b>Z</b>	29	BJ	W0066	604	22		33-16-17	ALL
	<b>Z</b>	29	BJ	W0066	60T	22		33-16-22	ALL
	<b>Z</b>	29	BJ	W0066	652	22		33-16-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 22

Jun 28/2006



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0066		<b>BACT44B1180D (continued)</b>					<b>0191/280/R008</b>		<b>ALL</b>
TB0066	X	<b>BACM15C3A (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	Y	<b>BACM15C3B (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	Z	<b>BACM15C3C (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
	Z	33	BJ	W0066	60F	22		33-16-12	ALL
	Z	33	BJ	W1309	006	22		33-16-17	ALL
	Z	34	BJ	W0062	05D	22		33-16-17	ALL
	Z	34	BJ	W0066	60G	22		33-16-12	ALL
	Z	34	BJ	W0066	704	22		33-16-17	ALL
	Z	34	BJ	W0863	010	22		33-16-17	ALL
	Z	34	BJ	W1309	007	22		33-16-17	ALL
	X	A002	BJ	W0066	69D	22		73-21-11	ALL
	X	A002	BJ	W0070	68L	22		73-21-11	ALL
	X	A003	BJ	W0062	75A	22		33-45-11	ALL
	X	A003	BJ	W0066	58V	22		33-45-11	ALL
	X	A007	BJ	W0066	61T	22		23-43-11	ALL
	X	A007	BJ	W0863	018	22		23-43-11	ALL
	X	A009	BJ	W0066	782	22		22-21-11	ALL
	X	A009	BJ	W1307	003	22		22-21-11	ALL
	X	A010	BJ	W0066	789	24		34-12-22	ALL
	X	A010	BJ	W1271	009	24		34-12-22	ALL
	X	A011	BJ	W0066	784	24		31-51-41	ALL
	X	A011	BJ	W1271	032	24		31-51-41	ALL
	X	A012	BJ	W0066	779	24		27-32-11	ALL
	X	A012	BJ	W1271	003	24		27-32-11	ALL
	X	A013	BJ	W0066	800	22		34-33-11	ALL
	X	A013	BJ	W1271	011	22		34-33-11	ALL
	X	A014	BJ	W0066	798	22		34-33-31	ALL
	X	A014	BJ	W1271	013	22		34-33-31	ALL
	Y	A015	BJ	W0066	01T	24		21-44-11	ALL
	Y	A015	BJ	W0066	50G	24		21-44-11	ALL
	Y	A015	BJ	W0066	50Y	24		21-44-11	ALL
	Y	A015	BJ	W0070	01F	24		21-44-11	ALL
	Y	A017	BJ	W0066	56E	24		30-21-11	ALL
	Y	A017	BJ	W0066	845	22		30-21-11	050-099, 150-199
	Y	A017	BJ	W0066	846	22		30-21-11	275-299
	Y	A017	BJ	W0066	851	22		30-21-11	275-299
	Y	A017	BJ	W0066	855	22		SPARE	050-099, 155-199
	Y	A017	BJ	W0066	890	22		30-21-11	050-099, 150-199
	Y	A018	BJ	W0066	56D	24		30-21-11	ALL
	Y	A018	BJ	W0066	56W	24		SPARE	050-099, 155-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 23

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0066		<b>BACT44B1180D (continued)</b>					<b>0191/280/R008</b>		<b>ALL</b>
TB0066	X	<b>BACM15C3A (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	Y	<b>BACM15C3B (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	Z	<b>BACM15C3C (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
	Y	A018	BJ	W0066	56W	24		30-21-11	275-299
	Y	A018	BJ	W0066	847	24		30-21-11	275-299
	Y	A018	BJ	W0066	848	24		30-21-11	050-099, 150-199
	Y	A018	BJ	W0066	851	22		30-21-11	050-099, 150-199
	Y	A020	BJ	W0066	613	24		28-22-12	050-099, 155-199, 276-299
	Y	A020	BJ	W0066	629	24		28-22-12	050-099, 155-199, 276-299
	Y	A020	BJ	W0066	630	24		28-22-12	050-099, 155-199, 276-299
	Y	A021	BJ	W0066	79R	22		30-11-11	050-099, 150-199
	Y	A021	BJ	W0066	79T	22		30-11-11	050-099, 150-199
	Y	A021	BJ	W0066	79V	22		30-11-11	050-099, 150-199
	Y	A022	BJ	W0066	51F	24		21-58-11	ALL
	Y	A022	BJ	W0723	020	24		21-58-11	ALL
	Y	A022	BJ	W0725	020	24		21-58-11	ALL
	Y	A022	BJ	W0751	020	24		21-58-11	ALL
	F	A025	2	W0062	739	18		33-43-11	150-199, 275-299
	F	A025	2	W0066	58R	18		33-43-11	150-199, 275-299
	F	A026	2	W0062	738	18		33-43-11	150-199, 275-299
	F	A026	2	W0066	58T	18		33-43-11	150-199, 275-299
	Y	A031	BJ	W0062	05C	22		33-16-17	ALL
	Y	A031	BJ	W0066	60B	22		33-16-12	ALL
	Y	A031	BJ	W0066	703	22		33-16-17	ALL
	Y	A035	BJ	W0066	01C	22		33-16-17	ALL
	Y	A035	BJ	W0066	60M	22		33-16-22	ALL
	Y	A036	BJ	W0066	60H	22		33-16-17	ALL
	Y	A036	BJ	W0725	018	22		33-16-17	ALL
	X	B002	BJ	W0066	69DZ			73-21-11	050-099, 162-199, 277-299
	X	B002	BJ	W0070	68LZ			73-21-11	050-099, 162-199, 277-299
	X	B003	BJ	W0066	64A	22		33-11-16	ALL
	X	B003	BJ	W0070	641	22		33-11-16	ALL
	X	B008	BJ	W0066	63L	20		22-21-21	ALL
	X	B008	BJ	W1309	001	20		22-21-21	ALL
	X	B009	BJ	W0066	788	22		34-12-12	ALL
	X	B009	BJ	W1271	007	22		34-12-12	ALL
	X	B010	BJ	W0066	777	24		34-46-12	ALL
	X	B010	BJ	W1271	036	24		34-46-12	ALL
	X	B011	BJ	W0066	783	24		31-51-42	ALL
	X	B011	BJ	W1271	018	24		31-51-42	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 24

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0066		<b>BACT44B1180D (continued)</b>					<b>0191/280/R008</b>		<b>ALL</b>
TB0066	X	<b>BACM15C3A (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	Y	<b>BACM15C3B (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	Z	<b>BACM15C3C (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
	X	B012	BJ	W0066	778	24		27-32-21	ALL
	X	B012	BJ	W1271	024	24		27-32-21	ALL
	X	B013	BJ	W0066	799	22		34-33-21	ALL
	X	B013	BJ	W1271	012	22		34-33-21	ALL
	X	B014	BJ	W0062	339B	24		21-61-71	ALL
	X	B014	BJ	W0066	339B	24		21-61-71	ALL
	X	C001	BJ	W0060	023	24		36-11-41	ALL
	X	C001	BJ	W0066	61D	24		36-11-41	ALL
	X	C003	BJ	W0062	79E	20		30-81-11	050-099, 150-199
	X	C003	BJ	W0066	79C	20		30-81-11	050-099, 150-199
	X	C005	BJ	W0062	068	20		21-31-21	ALL
	X	C005	BJ	W0066	50E	20		21-31-21	ALL
	X	C006	BJ	W0062	739	20		33-43-11	050-099
	X	C006	BJ	W0066	58R	20		33-43-11	050-099
	X	C008	BJ	W0062	05N	22		27-61-12	ALL
	X	C008	BJ	W1309	016	22		27-61-12	ALL
	X	C014	BJ	W0062	339R	24		21-61-71	ALL
	X	C014	BJ	W0066	339R	24		21-61-71	ALL
	Y	C015	BJ	W0066	51G	24		21-58-11	ALL
	Y	C015	BJ	W0070	13G	24		21-58-16	ALL
	Y	C015	BJ	W0863	007	24		21-58-11	ALL
	Y	C019	BJ	W0066	02C	24		21-26-21	ALL
	Y	C019	BJ	W0066	50H	24		21-44-21	ALL
	Y	C019	BJ	W0066	50J	24		21-44-21	ALL
	Y	C020	BJ	W0062	724	22		28-42-12	050-099, 155-199, 276-299
	Y	C020	BJ	W0066	618	22		28-42-12	050-099, 155-199, 276-299
	Y	C020	BJ	W0066	724	22		28-42-12	050-099, 155-199, 276-299
	Y	C031	BJ	W0066	60D	22		33-16-12	ALL
	Y	C031	BJ	W0863	009	22		33-16-17	ALL
	Y	C035	BJ	W0066	133	22		33-16-17	ALL
	Y	C035	BJ	W0066	503	22		33-16-17	ALL
	Y	C035	BJ	W0066	60N	22		33-16-22	ALL
	Y	C036	BJ	W0066	60J	22		33-16-17	ALL
	Y	C036	BJ	W0723	010	22		33-16-17	150-154, 275-299
	Y	C036	BJ	W0723	019	22		33-16-17	150-154, 275-299
	Y	C036	BJ	W0725	010	22		33-16-17	050-099, 155-199
	Y	C036	BJ	W0725	019	22		33-16-17	050-099, 155-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 25

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0066		<b>BACT44B1180D (continued)</b>					<b>0191/280/R008</b>		<b>ALL</b>
TB0066	X	<b>BACM15C3A (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	Y	<b>BACM15C3B (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
TB0066	Z	<b>BACM15C3C (continued)</b>					<b>0202/280/R008</b>		<b>ALL</b>
	X	D005	BJ	W0062	56V	22		30-43-11	ALL
	X	D005	BJ	W0066	589	22		30-43-11	ALL
	X	D006	BJ	W0062	738	20		33-43-11	050-099
	X	D006	BJ	W0066	58T	20		33-43-11	050-099
	X	D014	BJ	W0062	339Y	24		21-61-71	ALL
	X	D014	BJ	W0066	339Y	24		21-61-71	ALL
	Y	DED		W0062	05CZ			33-16-17	ALL
	Z	DED		W0062	05DZ			33-16-17	ALL
	X	DED		W0062	05NZ			27-61-12	ALL
	X	DED		W0062	56VZ			30-43-11	ALL
	Y	DED		W0062	724Z			28-42-12	050-099, 155-199, 276-299
	Y	DED		W0066	01CZ			33-16-17	ALL
	Y	DED		W0066	133Z			33-16-17	ALL
	Y	DED		W0066	503Z			33-16-17	ALL
	Y	DED		W0066	60BZ			33-16-12	ALL
	Y	DED		W0066	60DZ			33-16-12	ALL
	Y	DED		W0066	60MZ			33-16-22	ALL
	Y	DED		W0066	60NZ			33-16-22	ALL
	X	DED		W0066	69DZ			73-21-11	150-157, 275-276
	Y	DED		W0066	724Z			28-42-12	050-099, 155-199, 276-299
	X	DED		W0066	782Z			22-21-11	ALL
	X	DED		W0070	68LZ			73-21-11	150-157, 275-276
	Y	DED		W0723	010Z			33-16-17	150-154, 275-299
	Y	DED		W0723	019Z			33-16-17	150-154, 275-299
	Z	DED		W0863	006Z			21-58-11	ALL
	Y	DED		W0863	009Z			33-16-17	ALL
	Z	DED		W0863	010Z			33-16-17	ALL
<b>TB0068</b>		<b>BACT44B0780D</b>					<b>0190/284/L010</b>		<b>ALL</b>
<b>TB0068</b>	G	<b>BACM15C1B</b>					<b>P005-00/ /</b>		<b>ALL</b>
<b>TB0068</b>	H	<b>BACM15C2A</b>					<b>P005-00/ /</b>		<b>ALL</b>
<b>TB0068</b>	X	<b>BACM15C3A</b>					<b>P005-00/ /</b>		<b>ALL</b>
<b>TB0068</b>	Y	<b>BACM15C3B</b>					<b>P005-00/ /</b>		<b>ALL</b>
<b>TB0068</b>	Z	<b>BACM15C3C</b>					<b>P005-00/ /</b>		<b>ALL</b>
	H	1	2	W0062	09J	16		33-13-16	ALL
	H	1	2	W0062	131	20		33-13-16	ALL
	H	1	2	W0066	071	18		33-13-16	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 26

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0068		<b>BACT44B0780D (continued)</b>					<b>0190/284/L010</b>		<b>ALL</b>
TB0068	G	<b>BACM15C1B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	H	<b>BACM15C2A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	X	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	Y	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	Z	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	H	1	2	W0723	023	20		33-13-16	ALL
	H	1	2	W0725	023	20		33-13-16	ALL
	H	1	2	W0751	001	20		33-13-16	ALL
	Z	13	BJ	W0060	003	22		33-16-17	ALL
	Z	13	BJ	W0070	003	22		33-16-17	ALL
	Z	13	BJ	W0070	06E	22		33-16-22	ALL
	Z	13	BJ	W0070	583	22		33-16-17	ALL
	Z	14	BJ	W0066	653	22		33-16-17	ALL
	Z	14	BJ	W0070	06H	22		33-16-22	ALL
	Z	15	BJ	W0062	044	22		33-16-17	ALL
	Z	15	BJ	W0062	654	22		33-16-17	ALL
	Z	15	BJ	W0066	03D	22		33-16-17	ALL
	Z	15	BJ	W0066	129	22		33-16-17	ALL
	Z	15	BJ	W0070	06M	22		33-16-22	ALL
	Z	15	BJ	W0070	684	22		33-16-17	ALL
	Z	16	BJ	W0060	004	22		33-16-17	ALL
	Z	16	BJ	W0066	654	22		33-16-17	ALL
	Z	16	BJ	W0070	004	22		33-16-17	ALL
	Z	16	BJ	W0070	06K	22		33-16-22	ALL
	Z	16	BJ	W0070	584	22		33-16-17	ALL
	Z	21	BJ	W0062	112	22		33-16-17	ALL
	Z	21	BJ	W0062	134	22		33-16-17	ALL
	Z	21	BJ	W0070	05U	22		33-16-12	ALL
	Z	21	BJ	W0070	864	22		33-16-17	ALL
	Z	21	BJ	W0863	036	22		33-16-17	ALL
	Z	21	BJ	W1307	031	22		33-16-17	ALL
	Z	22	BJ	W0062	067	22		33-16-17	ALL
	Z	22	BJ	W0062	844	22		33-16-17	ALL
	Z	22	BJ	W0066	067	22		33-16-17	ALL
	Z	22	BJ	W0066	827	22		33-16-17	050-099, 150-199
	Z	22	BJ	W0066	844	22		33-16-17	ALL
	Z	22	BJ	W0070	05V	22		33-16-12	ALL
	Z	22	BJ	W0070	134	22		33-16-17	ALL
	Z	22	BJ	W0070	654	22		33-16-17	ALL
	H	3	2	W0062	09H	16		33-13-16	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 27

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0068		<b>BACT44B0780D (continued)</b>					<b>0190/284/L010</b>		<b>ALL</b>
TB0068	G	<b>BACM15C1B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	H	<b>BACM15C2A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	X	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	Y	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	Z	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	H	3	2	W0070	651	20		33-13-16	ALL
	H	3	2	W0070	855	20		33-13-16	ALL
	H	3	2	W0675	006	20		33-13-16	156-157, 166-199, 277-299
	H	3	2	W0863	034	20		33-13-16	ALL
	H	3	2	W1307	055	20		33-13-16	ALL
	H	3		W9030	006	20		33-13-16	150, 153-155, 162-165
	G	5	2	W0062	09B	16		33-13-16	ALL
	G	5	2	W0062	561	18		33-13-16	ALL
	G	5	2	W0066	01A	20		33-13-16	ALL
	G	5	2	W0683	001	18		33-13-16	ALL
	H	6	2	W0060	001	20		33-13-16	ALL
	H	6	2	W0062	109	20		33-13-16	ALL
	H	6	2	W0062	11H	16		33-13-16	ALL
	H	6	2	W0062	501	18		33-13-16	ALL
	H	6	2	W0066	126	20		33-13-16	ALL
	H	6	2	W0066	841	18		33-13-16	ALL
	H	6	2	W0070	681	20		33-13-16	ALL
	G	8	2	W0062	043	22		33-16-17	ALL
	G	8	2	W0066	03C	22		33-16-17	ALL
	G	8	2	W0066	128	22		33-16-17	ALL
	G	8	2	W0070	06C	22		33-16-22	ALL
	X	A009	BJ	W0070	867	22		27-61-12	ALL
	X	A009	BJ	W1307	008	22		27-61-12	ALL
	X	A012	BJ	W0062	057	20		21-31-11	ALL
	X	A012	BJ	W0070	13F	20		21-31-11	ALL
	Y	A017	BJ	W0066	681	22		33-16-17	ALL
	Y	A017	BJ	W0070	06A	22		33-16-22	ALL
	Y	A018	BJ	W0070	05W	22		33-16-17	ALL
	Y	A018	BJ	W0723	018	22		33-16-17	ALL
	Y	A019	BJ	W0062	066	22		33-16-17	ALL
	Y	A019	BJ	W0062	843	22		33-16-17	275-299
	Y	A019	BJ	W0066	826	22		33-16-17	050-099, 150-199
	Y	A019	BJ	W0070	05R	22		33-16-12	ALL
	Y	A019	BJ	W0070	133	22		33-16-17	275-299
	Y	A019	BJ	W0070	845	22		33-16-17	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 28

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0068		<b>BACT44B0780D (continued)</b>					<b>0190/284/L010</b>		<b>ALL</b>
TB0068	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	Y	A020	BJ	W0062	133	22		33-16-17	ALL
	Y	A020	BJ	W0070	05Z	22		33-16-12	ALL
	Y	A020	BJ	W0863	037	22		33-16-17	ALL
	Y	A020	BJ	W1307	030	22		33-16-17	ALL
	X	B010	BJ	W0070	11X	20		22-21-11	ALL
	X	B010	BJ	W1307	009	20		22-21-11	ALL
	X	C009	BJ	W0070	868	22		27-11-12	ALL
	X	C009	BJ	W1307	005	22		27-11-12	ALL
	X	C010	BJ	W0070	869	22		27-41-11	ALL
	X	C010	BJ	W1307	007	22		27-41-11	ALL
	Y	C017	BJ	W0062	653	22		33-16-17	ALL
	Y	C017	BJ	W0070	06L	22		33-16-22	ALL
	Y	C017	BJ	W0070	683	22		33-16-17	ALL
	Y	C018	BJ	W0070	05X	22		33-16-17	ALL
	Y	C018	BJ	W0723	010	22		33-16-17	050-099, 155-199
	Y	C018	BJ	W0723	019	22		33-16-17	050-099, 155-199
	Y	C018	BJ	W0725	010	22		33-16-17	150-154, 275-299
	Y	C018	BJ	W0725	019	22		33-16-17	150-154, 275-299
	Y	C019	BJ	W0066	066	22		33-16-17	ALL
	Y	C019	BJ	W0066	843	22		33-16-17	ALL
	Y	C019	BJ	W0070	05T	22		33-16-12	ALL
	Y	C019	BJ	W0070	653	22		33-16-17	ALL
	Y	C020	BJ	W0062	111	22		33-16-17	ALL
	Y	C020	BJ	W0070	05S	22		33-16-12	ALL
	Y	C020	BJ	W0070	05Z	22		33-16-12	ALL
	Y	C020	BJ	W0070	863	22		33-16-17	ALL
	X	D009	BJ	W0070	870	22		27-21-12	ALL
	X	D009	BJ	W1307	006	22		27-21-12	ALL
	X	D010	BJ	W0070	866	22		27-41-11	ALL
	X	D010	BJ	W1307	025	22		27-41-11	ALL
	Z	DED		W0060	003Z			33-16-17	ALL
	Z	DED		W0060	004Z			33-16-17	ALL
	G	DED		W0062	043Z			33-16-17	ALL
	Z	DED		W0062	044Z			33-16-17	ALL
	X	DED		W0062	057Z			21-31-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 29

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0068		<b>BACT44B0780D (continued)</b>					<b>0190/284/L010</b>		<b>ALL</b>
TB0068	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0068	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	Y	DED		W0062	066Z			33-16-17	ALL
	Y	DED		W0062	133Z			33-16-17	ALL
	Z	DED		W0062	134Z			33-16-17	ALL
	Y	DED		W0062	653Z			33-16-17	ALL
	Z	DED		W0062	654Z			33-16-17	ALL
	Y	DED		W0062	843Z			33-16-17	275-299
	G	DED		W0066	03CZ			33-16-17	ALL
	Y	DED		W0066	066Z			33-16-17	ALL
	Z	DED		W0066	653Z			33-16-17	ALL
	Z	DED		W0066	654Z			33-16-17	ALL
	Y	DED		W0066	681Z			33-16-17	ALL
	Y	DED		W0066	843Z			33-16-17	ALL
	Y	DED		W0070	05RZ			33-16-12	ALL
	Y	DED		W0070	05SZ			33-16-12	ALL
	Y	DED		W0070	05XZ			33-16-17	ALL
	Y	DED		W0070	06AZ			33-16-22	ALL
	G	DED		W0070	06CZ			33-16-22	ALL
	Y	DED		W0070	133Z			33-16-17	275-299
	Y	DED		W0070	863Z			33-16-17	ALL
	Y	DED		W0723	010Z			33-16-17	050-099, 155-199
	Y	DED		W0723	019Z			33-16-17	050-099, 155-199
	Y	DED		W0725	010Z			33-16-17	150-154, 275-299
	Y	DED		W0725	019Z			33-16-17	150-154, 275-299
	Z	DED		W0863	036Z			33-16-17	ALL
	Y	DED		W0863	037Z			33-16-17	ALL
<b>TB0070</b>		<b>BACT44B1180D</b>					<b>0190/284/L010</b>		<b>ALL</b>
<b>TB0070</b>	<b>F</b>	<b>BACM15C1A</b>					<b>0200/280/0000</b>		<b>ALL</b>
<b>TB0070</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P005-00/ /</b>		<b>ALL</b>
<b>TB0070</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P005-00/ /</b>		<b>ALL</b>
<b>TB0070</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P005-00/ /</b>		<b>ALL</b>
<b>TB0070</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P005-00/ /</b>		<b>ALL</b>
	Z	29	BJ	W0062	003	22		33-16-17	ALL
	Z	29	BJ	W0062	073	22		33-16-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 30

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0070		<b>BACT44B1180D (continued)</b>					<b>0190/284/L010</b>		<b>ALL</b>
TB0070	F	<b>BACM15C1A (continued)</b>					<b>0200/280/0000</b>		<b>ALL</b>
TB0070	G	<b>BACM15C1B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	X	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	Y	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	Z	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	Z	29	BJ	W0062	503	22		33-16-17	ALL
	Z	29	BJ	W0062	535	22		33-16-17	050-099, 155-199, 276-299
	Z	29	BJ	W0062	603	22		33-16-17	ALL
	Z	29	BJ	W0062	60L	22		33-16-22	ALL
	Z	29	BJ	W0062	677	22		33-16-17	ALL
	Z	29	BJ	W0066	182	22		33-16-17	ALL
	Z	30	BJ	W0062	004	22		33-16-17	ALL
	Z	30	BJ	W0062	074	22		33-16-17	ALL
	Z	30	BJ	W0062	536	22		33-16-17	050-099, 155-199, 276-299
	Z	30	BJ	W0062	604	22		33-16-17	ALL
	Z	30	BJ	W0062	60T	22		33-16-22	ALL
	Z	30	BJ	W0062	661	22		33-16-17	ALL
	Z	33	BJ	W0062	60D	22		33-16-12	ALL
	Z	33	BJ	W0066	05C	22		33-16-17	ALL
	Z	34	BJ	W0062	60G	22		33-16-12	ALL
	Z	34	BJ	W0062	634	22		33-16-17	ALL
	Z	34	BJ	W0062	704	22		33-16-17	ALL
	Z	34	BJ	W0066	05D	22		33-16-17	ALL
	Z	34	BJ	W0675	011	20		33-16-17	156-157, 166-199
	Z	34	%	W0675	011	20		33-16-17	277-299
	Z	34	BJ	W9030	011	20		33-16-17	150, 153-155, 162-165
	X	A002	BJ	W0062	69D	22		73-21-11	ALL
	X	A002	BJ	W0070	67H	22		73-21-11	ALL
	X	A004	BJ	W0062	150	24		21-61-81	ALL
	X	A004	BJ	W0066	90D	24		21-61-81	ALL
	X	A005	BJ	W0062	589	22		30-43-11	ALL
	X	A005	BJ	W0066	56V	22		30-43-11	ALL
	F	A007	2	W0062	58M	18		33-42-21	150-199, 275-299
	F	A007	2	W0070	623	18		33-42-21	150-199, 275-299
	X	A009	BJ	W0062	772	22		22-21-21	ALL
	X	A009	BJ	W1309	004	22		22-21-21	ALL
	Y	A015	BJ	W0062	016	22		29-11-31	ALL
	Y	A015	BJ	W0062	876	22		29-21-32	ALL
	Y	A015	BJ	W0062	886	22		29-11-31	ALL
	Y	A017	BJ	W0062	56E	24		30-21-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 31

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0070		<b>BACT44B1180D (continued)</b>					<b>0190/284/L010</b>		<b>ALL</b>
TB0070	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>0200/280/0000</b>		<b>ALL</b>
TB0070	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	Y	A017	BJ	W0062	841	22		SPARE	050-099, 155-199
	Y	A017	BJ	W0062	841	22		30-21-11	275-299
	Y	A017	BJ	W0062	852	22		30-21-11	ALL
	Y	A017	BJ	W0062	890	22		30-21-11	050-099, 150-199
	Y	A018	BJ	W0062	56D	24		30-21-11	275-299
	Y	A018	BJ	W0062	56W	24		30-21-11	275-299
	Y	A018	BJ	W0062	847	24		30-21-11	050-099, 150-199
	Y	A018	BJ	W0062	848	24		30-21-11	275-299
	Y	A018	BJ	W0062	857	24		30-21-11	050-099, 150-199
	Y	A018	BJ	W0062	870	24		30-21-11	050-099, 150-199
	Y	A021	BJ	W0062	613	24		28-22-12	050-099, 155-199, 276-299
	Y	A021	BJ	W0062	629	24		28-22-12	050-099, 155-199, 276-299
	Y	A021	BJ	W0062	630	24		28-22-12	050-099, 155-199, 276-299
	Y	A031	BJ	W0062	60A	22		33-16-12	ALL
	Y	A031	BJ	W0062	703	22		33-16-17	ALL
	Y	A031	BJ	W0675	010	20		33-16-17	156-157, 166-199
	Y	A031	%	W0675	010	20		33-16-17	277-299
	Y	A031	BJ	W9030	010	20		33-16-17	150, 153-155, 162-165
	Y	A032	BJ	W0062	507	22		33-16-17	ALL
	Y	A032	BJ	W0070	018	22		33-16-12	ALL
	Y	A036	BJ	W0062	60H	22		33-16-17	ALL
	Y	A036	BJ	W0751	018	22		33-16-17	ALL
	X	B002	BJ	W0062	69DZ			73-21-11	050-099, 162-199, 277-299
	X	B002	BJ	W0070	67HZ			73-21-11	050-099, 162-199, 277-299
	X	B009	BJ	W0062	644	24		34-61-14	050-099, 150-199, 276-299
	X	B009	BJ	W1307	100	24		34-61-14	050-099, 150-199, 276-299
	F	C007	2	W0062	58K	18		33-42-21	150-199, 275-299
	F	C007	2	W0070	622	18		33-42-21	150-199, 275-299
	Y	C015	BJ	W0062	58N	24		33-42-11	ALL
	Y	C015	BJ	W0062	732	24		33-42-11	ALL
	Y	C015	BJ	W0070	620	24		33-42-21	ALL
	Y	C016	BJ	W0070	14A	20		33-11-13	ALL
	Y	C016	BJ	W0070	14B	20		33-11-13	ALL
	Y	C016	BJ	W0070	613	20		33-11-13	ALL
	Y	C020	BJ	W0062	618	22		28-42-12	050-099, 155-199, 276-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 32

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0070		<b>BACT44B1180D (continued)</b>					<b>0190/284/L010</b>		<b>ALL</b>
TB0070	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>0200/280/0000</b>		<b>ALL</b>
TB0070	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	Y	C020	BJ	W0062	723	22		28-42-12	050-099, 155-199, 276-299
	Y	C020	BJ	W0066	723	22		28-42-12	050-099, 155-199, 276-299
	Y	C021	BJ	W0062	843	22		33-16-17	050-099, 150-199
	Y	C021	BJ	W0070	133	22		33-16-17	050-099, 150-199
	Y	C021	BJ	W0070	845	22		33-16-17	050-099, 150-199
	Y	C022	BJ	W0062	746	20		28-31-12	050-099, 155-199, 277-299
	Y	C022	BJ	W0062	748	20		28-31-12	050-099, 155-199, 277-299
	Y	C022	BJ	W0066	741	20		28-31-12	050-099, 155-199, 277-299
	Y	C031	BJ	W0062	60C	22		33-16-12	ALL
	Y	C031	BJ	W0062	633	22		33-16-17	ALL
	Y	C032	BJ	W0062	508	22		33-16-17	ALL
	Y	C032	BJ	W0070	019	22		33-16-12	ALL
	Y	C035	BJ	W0062	504	22		33-16-17	ALL
	Y	C035	BJ	W0062	60W	22		33-16-22	ALL
	Y	C035	BJ	W0066	183	22		33-16-17	ALL
	Y	C036	BJ	W0062	60J	22		33-16-17	ALL
	Y	C036	BJ	W0751	010	22		33-16-17	ALL
	Y	C036	BJ	W0751	019	22		33-16-17	ALL
	X	D001	BJ	W0062	58L	24		33-42-21	ALL
	X	D001	BJ	W0070	621	24		33-42-21	ALL
	X	D002	BJ	W0062	58M	20		33-42-21	050-099
	X	D002	BJ	W0070	623	20		33-42-21	050-099
	X	D003	BJ	W0062	58K	20		33-42-21	050-099
	X	D003	BJ	W0070	622	20		33-42-21	050-099
	X	D010	BJ	W0863	014	22		31-51-33	ALL
	X	D010	BJ	W1271	005	22		31-51-33	ALL
	Y	DED		W0062	016Z			29-11-31	ALL
	Y	DED		W0062	60AZ			33-16-12	ALL
	Y	DED		W0062	60CZ			33-16-12	ALL
	Y	DED		W0062	633Z			33-16-17	ALL
	X	DED		W0062	69DZ			73-21-11	150-157, 275-276
	Y	DED		W0062	703Z			33-16-17	ALL
	Y	DED		W0062	723Z			28-42-12	050-099, 155-199, 276-299
	Y	DED		W0062	746Z			28-31-12	050-099, 155-199, 277-299
	Y	DED		W0062	748Z			28-31-12	050-099, 155-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 33

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0070		<b>BACT44B1180D (continued)</b>					<b>0190/284/L010</b>		<b>ALL</b>
TB0070	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>0200/280/0000</b>		<b>ALL</b>
TB0070	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
TB0070	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P005-00/ /</b>		<b>ALL</b>
	X	DED		W0062	772Z			22-21-21	ALL
	Y	DED		W0062	843Z			33-16-17	050-099, 150-199
	Y	DED		W0062	886Z			29-11-31	ALL
	Z	DED		W0066	05CZ			33-16-17	ALL
	Z	DED		W0066	05DZ			33-16-17	ALL
	X	DED		W0066	56VZ			30-43-11	ALL
	Y	DED		W0066	723Z			28-42-12	050-099, 155-199, 276-299
	Y	DED		W0066	741Z			28-31-12	050-099, 155-199, 277-299
	Y	DED		W0070	133Z			33-16-17	050-099, 150-199
	X	DED		W0070	67HZ			73-21-11	150-157, 275-276
	X	DED		W1307	100Z			34-61-14	050-099, 150-199, 276-299
<b>TB0074</b>		<b>BACT44B0560U</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0074</b>	<b>D</b>	<b>DIODEBLOCK-REF284T0187-</b>					<b>P036-00/ /</b>		<b>050-099, 155-199, 276-299</b>
<b>TB0074</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
<b>TB0074</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
<b>TB0074</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0074</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0074</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W0176	003	24		32-09-11	ALL
	Z	10	BJ	W0176	08P	24		32-09-11	ALL
	Z	10	BJ	W0176	103	24		32-09-11	ALL
	Z	10	BJ	W0176	106	24		32-09-11	ALL
	Z	10	BJ	W0176	116	24		32-09-11	ALL
	Z	10	BJ	W0176	560	24		32-09-11	ALL
	Z	10	BJ	W0176	672	24		32-09-11	ALL
	Z	10	BJ	W0176	676	24		32-09-11	ALL
	Z	4	BJ	W0176	015	24		32-09-11	ALL
	Z	4	BJ	W0176	133	24		32-09-11	ALL
	Z	4	BJ	W0176	134	24		32-09-11	ALL
	Z	4	BJ	W0176	51Q	24		32-09-11	ALL
	Z	4	BJ	W0176	51R	24		32-09-11	ALL
	Z	4	BJ	W0176	549	24		32-09-11	ALL
	Z	5	BJ	W0176	010	24		32-09-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 34

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0074		<b>BACT44B0560U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0074	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 155-199, 276-299</b>
TB0074	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0074	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0074	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0074	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0074	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	5	BJ	W0176	05H	24		32-09-11	ALL
	Z	5	BJ	W0176	19L	24		32-09-11	ALL
	Z	5	BJ	W0176	519	24		32-09-11	ALL
	Z	5	BJ	W0176	589	24		32-09-11	ALL
	Z	5	BJ	W0176	668	24		32-09-11	ALL
	Y	A007	BJ	W0176	045	24		32-09-11	ALL
	Y	A007	BJ	W0176	04C	24		32-09-11	ALL
	Y	A007	BJ	W0176	04D	24		32-09-11	ALL
	Y	A008	BJ	W0176	645	24		27-51-31	ALL
	Y	A008	BJ	W0176	646	24		27-51-31	ALL
	Y	A008	BJ	W0176	647	24		27-51-31	ALL
	Y	A011	BJ	W0176	190	24		36-11-11	ALL
	Y	A011	BJ	W0176	193	24		36-11-11	ALL
	Y	A011	BJ	W0176	194	24		36-11-11	ALL
	Y	A012	BJ	W0176	74M	22		28-31-21	050-099, 155-199, 276-299
	Y	A012	BJ	W0176	74T	22		28-31-21	050-099, 162-164, 276
	Y	A012	BJ	W0176	74W	22		28-31-21	050-099, 155-199, 276-299
	Y	A012	BJ	W0176	74X	22		28-31-21	050-099, 155-199, 276-299
	D	A015	2	W0176	74X	22		28-31-21	050-099, 162-164, 276
	Y	C008	BJ	W0176	640	24		27-81-31	ALL
	Y	C008	BJ	W0176	641	24		27-81-31	ALL
	Y	C008	BJ	W0176	642	24		27-81-31	ALL
	Y	C011	BJ	W0176	030	24		36-11-31	ALL
	Y	C011	BJ	W0176	031	24		36-11-31	ALL
	Y	C011	BJ	W0176	034	24		36-11-31	ALL
	Y	C012	BJ	W0176	04E	24		32-09-11	ALL
	Y	C012	BJ	W0176	09G	24		32-09-11	ALL
	Y	C012	BJ	W0176	09H	24		32-09-11	ALL
	Y	C013	BJ	W0176	10A	24		21-45-21	ALL
	Y	C013	BJ	W0176	10E	24		21-25-11	ALL
	Y	C013	BJ	W0176	526	24		21-25-11	ALL
	Y	C014	BJ	W0176	09N	24		21-45-21	150-199, 275-299
	Y	C014	BJ	W0176	21G	24		21-45-24	150-157, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 35

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0074		<b>BACT44B0560U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0074	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 155-199, 276-299</b>
TB0074	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0074	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0074	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0074	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0074	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	C014	BJ	W0176	21J	24		21-45-21	150-199, 275-299
	Y	C014	BJ	W0176	30C	24		21-45-21	275-299
	D	C015	2	W0176	18D	20		24-51-72	050-099, 162-164, 276
	Z	DED		W0176	015Z			32-09-11	ALL
	Z	DED		W0176	133Z			32-09-11	ALL
	Z	DED		W0176	134Z			32-09-11	ALL
	Z	DED		W0176	51QZ			32-09-11	050-099, 150-156, 162-199, 275-299
	Z	DED		W0176	51RZ			32-09-11	050-099, 150-156, 162-199, 275-299
	Z	DED		W0176	549Z			32-09-11	ALL
<b>TB0076</b>		<b>BACT44B0560U</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0076</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
<b>TB0076</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0076</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0076</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0076</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z			W0176	100Z			78-34-11	ALL
	Z			W0176	22P	20		78-34-11	ALL
	Z			W0176	67KZ			78-34-11	ALL
	Z	10	BJ	W0176	100	20		78-34-11	ALL
	Z	10	BJ	W0176	120	24		78-34-11	ALL
	Z	10	BJ	W0176	67K	20		78-34-11	ALL
	Z	10	BJ	W0176	812	24		78-34-11	ALL
	Z	10	BJ	W0176	813	24		78-34-11	ALL
	Z	11	BJ	W0176	004	24		32-09-11	ALL
	Z	11	BJ	W0176	08B	24		32-09-11	ALL
	Z	11	BJ	W0176	08R	24		32-09-11	ALL
	Z	11	BJ	W0176	559	24		32-09-11	ALL
	Z	11	BJ	W0176	673	24		32-09-11	ALL
	Z	11	BJ	W0176	677	24		32-09-11	ALL
	Z	12	BJ	W0176	001	24		21-53-11	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 36

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0076		<b>BACT44B0560U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0076	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	12	BJ	W0176	01R	24		21-53-11	050-099
	Z	12	BJ	W0176	24A	24		21-51-11	050-099
	Z	12	BJ	W0182	003	24		21-53-11	050-099
	Z	12	BJ	W0182	007	24		21-53-11	050-099
	Z	13	BJ	W0056	073	24		21-66-11	050-099
	Z	13	BJ	W0056	073	22		21-66-11	162-199
	Z	13	BJ	W0176	44A	22		21-66-11	050-099, 162-199
	Z	13	BJ	W0176	79A	22		21-66-11	050-099, 162-199
	Z	13	BJ	W0176	83A	22		21-66-11	050-099, 162-199
	Z	13	BJ	W0176	88A	22		21-66-11	050-099, 162-199
	Z	7	BJ	W0176	038	24		32-09-11	ALL
	Z	7	BJ	W0176	04H	24		32-09-13	ALL
	Z	7	BJ	W0176	102	24		32-09-11	ALL
	Z	7	BJ	W0176	110	24		32-09-11	ALL
	Z	7	BJ	W0176	113	24		32-09-11	050-099, 150-199, 277-299
	Z	7	BJ	W0176	117	24		32-09-11	ALL
	Z	7	BJ	W0176	19M	24		32-09-11	275-276
	Z	7	BJ	W0176	19N	24		32-09-11	ALL
	Z	8	BJ	W0176	005	24		32-09-11	ALL
	Z	8	BJ	W0176	039	24		32-09-11	ALL
	Z	8	BJ	W0176	04B	24		32-09-11	ALL
	Z	8	BJ	W0176	05J	24		32-09-11	ALL
	Z	8	BJ	W0176	113	24		32-09-11	ALL
	Z	8	BJ	W0176	667	24		32-09-11	ALL
	Z	8	BJ	W0176	678	24		32-09-11	ALL
	Z	9	BJ	W0176	104	24		32-09-11	ALL
	Z	9	BJ	W0176	105	24		32-09-11	ALL
	Z	9	BJ	W0176	109	24		32-09-11	ALL
	Z	9	BJ	W0176	118	24		32-09-11	ALL
	Z	9	BJ	W0176	123	24		32-09-11	ALL
	Z	9	BJ	W0176	589	24		32-09-11	ALL
	X	A001	BJ	W0176	871	22		21-51-11	ALL
	X	A001	BJ	W0182	505	22		21-51-11	ALL
	X	A002	BJ	W0176	73P	22		21-45-22	ALL
	X	A002	BJ	W0180	70A	22		21-45-22	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 37

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0076		<b>BACT44B0560U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0076	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	A003	BJ	W0176	037	24		32-09-11	ALL
	Y	A003	BJ	W0176	08A	24		32-09-11	ALL
	Y	A003	BJ	W0176	675	24		32-09-11	ALL
	Y	A004	BJ	W0176	113	24		32-09-11	275-276
	Y	A004	BJ	W0176	116	24		32-09-11	ALL
	Y	A004	BJ	W0176	19M	24		32-09-11	050-099, 150-199, 277-299
	Y	A004	BJ	W0176	19N	24		32-09-11	ALL
	Y	A005	BJ	W0176	001	24		21-53-11	150-199, 275-299
	Y	A005	BJ	W0176	01R	24		21-53-11	150-199, 275-299
	Y	A005	BJ	W0176	14V	24		21-61-51	050-099
	Y	A005	BJ	W0176	24B	24		21-61-51	050-099
	Y	A005	BJ	W0176	24R	24		21-51-11	050-099
	Y	A005	BJ	W0182	003	24		21-53-11	150-199, 275-299
	Y	A005	BJ	W0182	007	24		21-53-11	150-199, 275-299
	Y	A006	BJ	W0176	046	22		22-14-31	ALL
	Y	A006	BJ	W0176	511	22		22-14-31	ALL
	Y	A006	BJ	W0176	512	22		22-14-31	ALL
	F	A015	2	W0180	145	18		38-32-11	275-276
	F	A015	2	W0182	172	18		38-32-11	275-276
	X	B001	BJ	W0176	872	22		21-51-11	ALL
	X	B001	BJ	W0182	506	22		21-51-11	ALL
	X	C001	BJ	W0176	01P	24		21-53-11	ALL
	X	C001	BJ	W0182	055	24		21-53-11	ALL
	Y	C003	BJ	W0176	071	24		33-16-14	ALL
	Y	C003	BJ	W0176	072	24		33-16-14	ALL
	Y	C003	BJ	W0176	073	24		33-16-14	ALL
	Y	C003	BJ	W0176	877	24		33-16-14	ALL
	Y	C004	BJ	W0176	002	24		21-53-11	ALL
	Y	C004	BJ	W0176	01Q	24		21-53-11	ALL
	Y	C004	BJ	W0182	004	24		21-53-11	ALL
	Y	C004	BJ	W0182	008	24		21-53-11	ALL
	Y	C006	BJ	W0176	047	22		22-14-31	ALL
	Y	C006	BJ	W0176	513	22		22-14-31	ALL
	Y	C006	BJ	W0176	514	22		22-14-31	ALL
	F	C015	2	W0182	173	18		38-32-11	275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 38

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0076		<b>BACT44B0560U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0076	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0076	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	F	C015	2	W0184	70T	18		38-32-11	275-276
	Y	DED		W0176	037Z			32-09-11	ALL
	Y	DED		W0176	08AZ			32-09-11	ALL
	Y	DED		W0176	675Z			32-09-11	ALL
TB0078		<b>BACT44B0560U</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	F	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0078	G	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	X	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0078	Y	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	Z	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W0184	064	24		21-58-16	ALL
	Z	10	BJ	W0184	080	24		21-58-16	ALL
	Z	10	BJ	W0184	083	24		21-58-16	ALL
	Z	10	BJ	W0184	586	24		21-58-12	ALL
	Z	10	BJ	W0184	589	24		21-58-16	ALL
	Z	10	BJ	W0184	590	24		21-58-16	ALL
	Z	10	BJ	W0184	593	24		21-58-16	ALL
	Z	10	BJ	W0184	75S	24		21-58-12	ALL
	G	15	2	W0184	105	18		28-21-11	ALL
	G	15	2	W0184	106	18		28-21-11	ALL
	G	15	2	W0184	107	18		28-21-11	ALL
	G	15	2	W0184	762	22		28-22-12	ALL
	G	16	2	W0184	100	18		28-21-11	ALL
	G	16	2	W0184	101	22		28-21-11	ALL
	G	16	2	W0184	535	18		28-21-11	ALL
	Z	5	BJ	W0184	145	20		28-21-13	ALL
	Z	5	BJ	W0184	146	20		28-21-13	ALL
	Z	5	BJ	W0184	148	20		28-21-13	ALL
	Z	5	BJ	W0184	150	20		28-21-13	ALL
	Z	5	BJ	W0184	152	20		28-21-13	ALL
	Z	5	BJ	W0184	154	20		28-21-13	ALL
	Z	5	BJ	W0184	155	20		28-21-13	ALL
	Z	6	BJ	W0176	849	24		29-11-32	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 39

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0078		<b>BACT44B0560U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0078	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0078	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	6	BJ	W0184	657	22		29-11-32	ALL
	Z	6	BJ	W0184	669	24		29-11-32	ALL
	Z	6	BJ	W0184	672	24		29-11-32	ALL
	Z	6	BJ	W0184	701	24		29-11-32	ALL
	Z	6	BJ	W0184	841	24		29-11-32	ALL
	Z	6	BJ	W0184	870	22		29-11-32	ALL
	Y	A001	BJ	W0176	17J	24		31-31-26	ALL
	Y	A001	BJ	W0180	135	24		31-31-26	ALL
	Y	A002	BJ	W0184	117	22		28-21-11	ALL
	Y	A002	BJ	W0184	118	22		28-21-11	ALL
	Y	A002	BJ	W0184	119	20		28-21-11	ALL
	Y	A003	BJ	W0184	127	22		28-21-11	ALL
	Y	A003	BJ	W0184	130	20		28-21-11	ALL
	Y	A003	BJ	W0184	534	22		28-21-11	ALL
	Y	A004	BJ	W0184	131	22		28-21-12	ALL
	Y	A004	BJ	W0184	132	22		28-21-12	ALL
	Y	A004	BJ	W0184	133	22		28-21-12	ALL
	Y	A004	BJ	W0184	134	22		28-21-12	ALL
	Y	A008	BJ	W0176	20U	22		30-21-11	050-099, 150-199
	Y	A008	BJ	W0176	20Y	22		30-21-11	050-099, 150-199
	Y	A008	BJ	W0176	21H	24		30-81-11	050-099, 150-199
	Y	A011	BJ	W0184	519	22		29-11-32	ALL
	Y	A011	BJ	W0184	638	24		29-11-32	ALL
	Y	A011	BJ	W0184	642	24		29-11-32	ALL
	Y	A013	BJ	W0184	062	22		21-58-16	ALL
	Y	A013	BJ	W0184	754	22		21-58-16	ALL
	Y	A013	BJ	W0184	776	22		21-58-16	ALL
	Y	A014	BJ	W0184	166	24		80-11-11	ALL
	Y	A014	BJ	W0184	167	24		80-11-11	ALL
	Y	A014	BJ	W0184	170	24		80-11-11	ALL
	Y	C001	BJ	W0176	17K	24		31-31-26	ALL
	Y	C001	BJ	W0184	178	20		76-11-11	ALL
	Y	C001	BJ	W0184	51A	20		76-11-11	ALL
	Y	C002	BJ	W0184	122	22		28-21-11	ALL
	Y	C002	BJ	W0184	123	22		28-21-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 40

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0078		<b>BACT44B0560U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0078	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0078	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0078	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	C002	BJ	W0184	124	20		28-21-11	ALL
	Y	C003	BJ	W0184	109	22		28-21-11	ALL
	Y	C003	BJ	W0184	758	22		28-21-11	ALL
	Y	C003	BJ	W0184	761	22		28-22-12	ALL
	Y	C008	BJ	W0184	648	22		29-11-32	ALL
	Y	C008	BJ	W0184	654	22		29-11-32	ALL
	Y	C008	BJ	W0184	656	22		29-11-32	ALL
	Y	C013	BJ	W0184	518	22		29-11-32	ALL
	Y	C013	BJ	W0184	685	24		29-11-32	ALL
	Y	C013	BJ	W0184	840	24		29-11-32	ALL
	Y	C014	BJ	W0184	063	22		21-58-16	ALL
	Y	C014	BJ	W0184	434	22		21-58-16	ALL
	Y	C014	BJ	W0184	755	22		21-58-16	ALL
	Z	DED		W0176	849Z			29-11-32	ALL
TB0080		<b>BACT44B0560U</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	D	<b>DIODEBLOCK-REF284T0187-</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	F	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0080	G	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	X	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	Y	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	Z	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>ALL</b>
	X			W0176	22RZ			78-34-21	ALL
	X			W0176	22TZ			78-34-21	ALL
	X			W0176	GRK			78-34-21	ALL
	X			W0180	160Z			78-34-21	ALL
	X			W0180	161Z			78-34-21	ALL
	X			W0180	GRK			78-34-21	ALL
	G	10	2	W0184	518	22		29-11-32	ALL
	G	10	2	W0184	659	18		29-11-32	ALL
	G	10	2	W0184	839	18		29-11-32	ALL
	Z	3	BJ	W0184	785	22		32-42-11	ALL
	Z	3	BJ	W0184	786	22		32-42-11	ALL
	Z	3	BJ	W0184	787	24		32-42-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 41

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0080		<b>BACT44B0560U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0080	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0080	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	3	BJ	W0184	788	22		32-42-11	ALL
	Z	3	BJ	W0184	789	22		32-42-11	ALL
	Z	3	BJ	W0184	790	22		32-42-11	ALL
	Z	4	BJ	W0176	11E	24		73-21-11	155-199, 277-299
	Z	4	BJ	W0184	01P	24		76-11-11	155-199, 277-299
	Z	4	BJ	W0184	171	20		76-11-11	155-199, 277-299
	Z	4	BJ	W0184	172	20		76-11-11	155-199, 277-299
	Z	4	BJ	W0184	175	24		76-11-11	155-199, 277-299
	Z	4	BJ	W0184	182	20		76-11-11	155-199, 277-299
	D	A001	2	W0184	649	22		29-11-32	ALL
	D	A002	2	W0184	519	22		29-11-32	ALL
	Y	A006	BJ	W0176	51F	24		21-58-12	ALL
	Y	A006	BJ	W0184	587	24		21-58-16	ALL
	Y	A006	BJ	W0184	593	24		21-58-16	ALL
	Y	A006	BJ	W0184	851	24		21-58-16	ALL
	D	A011	2	W0176	839	22		30-21-11	ALL
	D	A012	2	W0176	70M	24		21-58-11	ALL
	X	A015	BJ	W0176	22R	20		78-34-21	ALL
	X	A015	BJ	W0180	160	20		78-34-21	ALL
	X	B015	BJ	W0176	22T	20		78-34-21	ALL
	X	B015	BJ	W0180	161	20		78-34-21	ALL
	D	C001	2	W0184	647	22		29-11-32	ALL
	D	C002	2	W0184	841	24		29-11-32	ALL
	Y	C006	BJ	W0176	93P	24		36-11-61	150-154
	Y	C006	BJ	W0176	93P	24		SPARE	275
	D	C011	2	W0176	274	22		30-21-11	ALL
	D	C012	2	W0176	15K	24		21-58-11	ALL
	X	C015	BJ	W0176	GRK			78-34-21	ALL
	X	C015	BJ	W0180	GRK			78-34-21	ALL
	Y	DED		W0176	51FZ			21-58-12	155-199
	Z	DED		W0184	01PZ			76-11-11	155-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 42

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0082		BACT44B0560U					P037-00/ /		ALL
TB0082	D	DIODEBLOCK-REF284T0188-					P037-00/ /		ALL
TB0082	F	BACM15C1A					P037-00/ /		150-199, 275-299
TB0082	G	BACM15C1B					P037-00/ /		ALL
TB0082	X	BACM15C3A					P037-00/ /		150-199, 275-299
TB0082	Y	BACM15C3B					P037-00/ /		ALL
TB0082	Z	BACM15C3C					P037-00/ /		ALL
	G	10	2	W0192	574	20		27-81-21	ALL
	G	10	2	W0192	655	22		27-81-21	ALL
	G	11	2	W0192	199	22		27-81-11	ALL
	G	11	2	W0192	558	22		27-81-11	ALL
	Z	13	BJ	W0188	039	24		21-61-41	ALL
	Z	13	BJ	W0192	15I	22		21-61-41	ALL
	Z	13	BJ	W0192	15N	22		21-61-41	ALL
	Z	13	BJ	W0192	15P	22		21-61-41	ALL
	Z	13	BJ	W0192	15Q	24		21-61-41	ALL
	Z	13	BJ	W0192	15R	24		21-61-41	ALL
	Z	14	BJ	W0192	12F	24		29-11-12	ALL
	Z	14	BJ	W0192	715	24		29-11-12	ALL
	Z	14	BJ	W0192	717	24		29-11-12	ALL
	Z	14	BJ	W0192	789	24		29-11-12	ALL
	Z	14	BJ	W0192	886	24		29-11-12	ALL
	Z	7	BJ	W0192	035	24		32-09-12	ALL
	Z	7	BJ	W0192	056	24		32-09-12	ALL
	Z	7	BJ	W0192	09J	24		32-09-12	ALL
	Z	7	BJ	W0192	505	24		32-09-12	ALL
	Z	7	BJ	W0192	68Y	24		32-09-12	ALL
	Z	7	BJ	W0192	747	24		32-09-12	ALL
	Z	7	BJ	W0192	813	24		32-09-12	ALL
	Z	7	BJ	W0192	849	24		32-09-12	ALL
	Z	8	BJ	W0192	15B	24		32-09-12	ALL
	Z	8	BJ	W0192	586	24		32-09-12	ALL
	Z	8	BJ	W0192	710	24		32-09-12	ALL
	Z	8	BJ	W0192	712	24		32-09-12	ALL
	Z	8	BJ	W0192	744	24		32-09-12	ALL
	G	9	2	W0192	02D	16		33-45-11	ALL
	G	9	2	W0192	02E	16		33-45-11	ALL
	G	9	2	W0192	02F	22		33-45-11	ALL
	G	9	2	W0192	02H	22		33-45-11	ALL
	Y	A001	BJ	W0188	042	24		21-61-41	ALL
	Y	A001	BJ	W0192	15T	24		21-61-41	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 43

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0082		<b>BACT44B0560U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0082	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0082	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0082	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0082	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0082	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0082	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	A001	BJ	W0192	16H	24		21-61-41	ALL
	Y	A002	BJ	W0192	68X	24		32-09-12	ALL
	Y	A002	BJ	W0192	68Y	24		32-09-12	ALL
	Y	A002	BJ	W0192	755	24		32-09-12	ALL
	Y	A003	BJ	W0192	63G	24		28-22-12	050-099, 155-199, 276-299
	Y	A003	BJ	W0192	79H	24		28-22-12	050-099, 155-199, 276-299
	Y	A003	BJ	W0198	189	24		28-22-12	050-099, 155-199, 276-299
	Y	A003	BJ	W0198	520	24		28-22-12	050-099, 155-199, 276-299
	Y	A004	BJ	W0192	63K	22		28-31-21	050-099, 155-199, 276-299
	Y	A004	BJ	W0192	64G	22		28-31-21	050-099, 162-164, 276
	Y	A004	BJ	W0192	64J	22		28-31-21	050-099, 155-199, 276-299
	Y	A004	BJ	W0192	64K	22		28-31-21	050-099, 155-199, 276-299
	Y	A005	BJ	W0192	105	22		29-11-12	ALL
	Y	A005	BJ	W0192	507	22		29-11-12	ALL
	Y	A005	BJ	W0192	834	22		29-11-12	ALL
	Y	A005	BJ	W0192	876	22		29-11-12	ALL
	Y	A006	BJ	W0192	020	24		32-09-12	ALL
	Y	A006	BJ	W0192	021	24		32-09-12	ALL
	Y	A006	BJ	W0192	518	24		32-09-12	ALL
	D	A012	2	W0192	12G	24		29-11-12	ALL
	D	A012	2	W0192	721	22		29-11-12	ALL
	D	A012	2	W0192	795	24		29-11-12	ALL
	D	A016	2	W0192	15F	24		21-61-41	ALL
	D	A016	2	W0192	15G	24		21-61-41	ALL
	Y	C001	BJ	W0192	696	24		21-26-11	ALL
	Y	C001	BJ	W0192	757	24		21-26-11	ALL
	Y	C001	BJ	W0192	759	24		21-26-11	ALL
	Y	C004	BJ	W0192	714	24		29-11-12	ALL
	Y	C004	BJ	W0192	720	24		29-11-12	ALL
	Y	C004	BJ	W0192	791	24		29-11-12	ALL
	Y	C005	BJ	W0192	15G	24		21-61-41	ALL
	Y	C005	BJ	W0192	15H	24		21-61-41	ALL
	Y	C005	BJ	W0192	15U	24		21-61-41	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 44

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0082		<b>BACT44B0560U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0082	D	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0082	F	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0082	G	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0082	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0082	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0082	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	C006	BJ	W0192	196	24		32-09-12	ALL
	Y	C006	BJ	W0192	839	24		32-09-12	ALL
	Y	C006	BJ	W0192	849	24		32-09-12	ALL
	D	C012	2	W0192	12F	24		29-11-12	ALL
	D	C012	2	W0192	12H	24		29-11-12	ALL
	D	C016	2	W0192	15D	24		21-61-41	ALL
	D	C016	2	W0192	15E	24		21-61-41	ALL
TB0084		<b>BACT44B0560U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	F	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0084	G	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	X	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0084	Y	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	Z	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z			W0192	013Z			78-34-21	ALL
	Z			W0192	07AZ			78-34-21	ALL
	Z			W0192	24RZ			78-34-21	ALL
	Z			W0192	78EZ			78-34-21	ALL
	Z			W0192	78F	20		78-34-21	ALL
	Z			W0192	78K	20		78-34-21	ALL
	Z	10	BJ	W0192	033	24		32-09-12	ALL
	Z	10	BJ	W0192	052	24		32-09-12	ALL
	Z	10	BJ	W0192	053	24		32-09-12	ALL
	Z	10	BJ	W0192	057	24		32-09-12	ALL
	Z	10	BJ	W0192	08L	24		32-61-14	ALL
	Z	10	BJ	W0192	517	24		32-09-12	ALL
	Z	10	BJ	W0192	591	24		32-09-12	ALL
	Z	10	BJ	W0192	748	24		32-09-12	ALL
	G	11	2	W0192	569	18		27-81-21	ALL
	G	11	2	W0192	576	18		27-81-21	ALL
	G	11	2	W0192	577	22		27-81-21	ALL
	G	12	2	W0192	553	18		27-81-11	ALL
	G	12	2	W0192	564	18		27-81-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 45

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0084		<b>BACT44B0560U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0084	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0084	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	G	12	2	W0192	565	22		27-81-11	ALL
	Z	13	BJ	W0192	053	24		32-09-12	ALL
	Z	13	BJ	W0192	585	24		32-09-12	ALL
	Z	13	BJ	W0192	61P	24		32-09-12	ALL
	Z	13	BJ	W0192	698	24		32-09-13	ALL
	Z	13	BJ	W0192	709	24		32-09-12	ALL
	Z	13	BJ	W0192	711	24		32-09-12	ALL
	Z	13	BJ	W0192	743	24		32-09-12	ALL
	Z	14	BJ	W0192	06X	24		78-36-21	ALL
	Z	14	BJ	W0192	07A	20		78-34-21	ALL
	Z	14	BJ	W0192	157	24		78-34-21	050-099
	Z	14	BJ	W0192	157	22		78-34-21	150-199, 275-299
	Z	14	BJ	W0192	24R	20		78-34-21	ALL
	Z	14	BJ	W0192	24T	24		78-34-21	050-099
	Z	14	BJ	W0192	24T	22		78-34-21	150-199, 275-299
	Z	3	BJ	W0192	013	20		78-34-21	ALL
	Z	3	BJ	W0192	188	24		78-34-21	ALL
	Z	3	BJ	W0192	548	24		78-34-21	ALL
	Z	3	BJ	W0192	549	24		78-34-21	ALL
	Z	3	BJ	W0192	78E	20		78-34-21	ALL
	Z	4	BJ	W0192	015	24		32-09-12	ALL
	Z	4	BJ	W0192	022	24		32-09-12	ALL
	Z	4	BJ	W0192	032	24		32-09-12	ALL
	Z	4	BJ	W0192	051	24		32-09-12	ALL
	Z	4	BJ	W0192	054	24		32-09-12	ALL
	Z	9	BJ	W0192	014	24		32-09-12	ALL
	Z	9	BJ	W0192	023	24		32-09-12	ALL
	Z	9	BJ	W0192	034	24		32-09-12	ALL
	Z	9	BJ	W0192	050	24		32-09-12	ALL
	Z	9	BJ	W0192	052	24		32-09-12	ALL
	Z	9	BJ	W0192	09K	24		32-09-12	ALL
	Z	9	BJ	W0192	753	24		32-09-12	ALL
	Z	9	BJ	W0192	835	24		32-09-12	ALL
	Y	A001	BJ	W0192	14D	22		27-81-11	ALL
	Y	A001	BJ	W0192	14E	22		27-81-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 46

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0084		<b>BACT44B0560U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	F	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0084	G	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0084	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	A001	BJ	W0192	14H	22		27-81-21	ALL
	Y	A002	BJ	W0192	09T	24		29-11-12	ALL
	Y	A002	BJ	W0192	11H	24		29-11-12	ALL
	Y	A002	BJ	W0192	11J	24		29-11-12	ALL
	F	A005	2	W0058	50A	18		23-32-31	275-299
	F	A005	2	W0192	50X	18		23-32-31	275-299
	F	A006	2	W0058	50C	18		23-32-51	275-299
	F	A006	2	W0192	50R	18		23-32-51	275-299
	Y	A007	BJ	W0192	025	22		22-14-31	ALL
	Y	A007	BJ	W0192	027	22		22-14-31	ALL
	Y	A007	BJ	W0192	513	22		22-14-31	ALL
	Y	A008	BJ	W0192	195	24		32-09-12	ALL
	Y	A008	BJ	W0192	833	24		32-09-12	ALL
	Y	A008	BJ	W0192	835	24		32-09-12	ALL
	Y	A008	BJ	W0192	838	24		32-09-12	ALL
	D	A015	2	W0192	19J	24		21-45-21	ALL
	D	A015	2	W0192	19K	24		21-45-21	ALL
	D	A016	2	W0192	19K	24		21-45-21	ALL
	D	A016	2	W0192	19L	24		21-45-21	ALL
	Y	C001	BJ	W0192	055	24		32-09-12	ALL
	Y	C001	BJ	W0192	16E	24		32-09-12	ALL
	Y	C001	BJ	W0192	16G	24		32-09-12	ALL
	Y	C002	BJ	W0192	178	24		32-09-12	ALL
	Y	C002	BJ	W0192	587	24		32-09-12	ALL
	Y	C002	BJ	W0192	61P	24		32-09-12	ALL
	Y	C002	BJ	W0192	68W	24		32-09-12	ALL
	F	C005	2	W0058	50B	18		23-32-41	275-299
	F	C005	2	W0192	50P	18		23-32-41	275-299
	F	C006	2	W0058	50D	18		23-32-61	275-299
	F	C006	2	W0192	50U	18		23-32-61	275-299
	Y	C007	BJ	W0192	029	22		22-14-31	ALL
	Y	C007	BJ	W0192	031	22		22-14-31	ALL
	Y	C007	BJ	W0192	514	22		22-14-31	ALL
	Y	C008	BJ	W0192	017	24		36-11-21	ALL
	Y	C008	BJ	W0192	019	24		36-11-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 47

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0084		<b>BACT44B0560U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0084	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0084	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0084	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	C008	BJ	W0192	133	24		36-11-21	ALL
	D	C015	2	W0192	19M	24		21-45-21	ALL
	D	C016	2	W0192	19N	24		21-45-21	ALL
TB0086		<b>BACT44B0405U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0086	<b>D</b>	<b>DIODEBLOCK-REF284T0188-</b>					<b>P037-00/ /</b>		<b>050-099, 150-155, 157-165, 275-276</b>
TB0086	<b>F</b>	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0086	<b>G</b>	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0086	<b>X</b>	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0086	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0086	<b>Z</b>	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	A001	BJ	W0198	120	24		80-11-21	ALL
	Y	A001	BJ	W0198	122	24		80-11-21	ALL
	Y	A001	BJ	W0198	170	24		80-11-21	ALL
	Y	A002	BJ	W0198	079	24		28-25-11	ALL
	Y	A002	BJ	W0198	080	24		28-25-11	ALL
	Y	A002	BJ	W0198	086	24		28-25-11	ALL
	Y	A003	BJ	W0198	156R	20		26-22-21	ALL
	Y	A003	BJ	W0198	157R	20		26-22-21	ALL
	Y	A003	BJ	W0198	159R	20		49-61-11	ALL
	Y	A004	BJ	W0198	076	24		28-25-11	ALL
	Y	A004	BJ	W0198	092	24		28-25-11	ALL
	Y	A004	BJ	W0198	555	24		28-25-11	ALL
	D	A006	2	W0192	65Q	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	C002	BJ	W0198	081	24		28-25-11	ALL
	Y	C002	BJ	W0198	082	24		28-25-11	ALL
	Y	C002	BJ	W0198	083	24		28-25-11	ALL
	Y	C003	BJ	W0198	075	24		28-25-11	ALL
	Y	C003	BJ	W0198	078	24		28-25-11	ALL
	Y	C003	BJ	W0198	085	24		28-25-11	ALL
	Y	C003	BJ	W0198	554	24		28-25-11	ALL
	Y	C004	BJ	W0198	016	22		49-61-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 48

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0086		<b>BACT44B0405U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0086	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 150-155, 157-165, 275-276</b>
TB0086	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0086	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0086	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0086	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0086	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	C004	BJ	W0198	017	20		49-61-11	ALL
	Y	C004	BJ	W0198	069	20		49-61-11	ALL
	D	C005	2	W0198	14H	24		SPARE	150
	D	C006	2	W0192	0AJ	22		36-11-62	050-099, 150-156, 162-166, 275-276
	D	C006	2	W0192	65W	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	C007	BJ	W0198	026	24		SPARE	150
	Y	C007	BJ	W0198	027	24		SPARE	150
	Y	C007	BJ	W0198	14H	24		SPARE	150
	Y	C008	BJ	W0198	129	20		76-11-11	ALL
	Y	C008	BJ	W0198	185	24		31-31-26	ALL
	Y	C008	BJ	W0198	187	20		76-11-11	ALL
TB0088		<b>BACT44B0680U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>D</b>	<b>DIODEBLOCK-REF284T0188-</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>F</b>	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0088	<b>G</b>	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>050-099, 150-199, 275-276, 280-299</b>
TB0088	<b>H</b>	<b>BACM15C2A</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0088	<b>X</b>	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0088	<b>Z</b>	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
	D	A001	2	W0192	03N	24		21-61-21	ALL
	D	A001	2	W0192	730	24		21-61-21	ALL
	D	A002	2	W0192	03Q	24		21-61-31	ALL
	D	A002	2	W0192	761	24		21-61-31	ALL
	D	A003	2	W0192	516	24		21-58-16	150-152, 275-276
	D	A003	2	W1118	109	22		25-33-11	153-154
	D	A003	2	W1118	525	22		25-33-11	050-099, 155-199, 277-299
	D	A004	2	W1118	107	22		25-33-11	155-199, 277-299
	D	A004	2	W1118	520	22		25-33-11	050-099, 153-154

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 49

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0088		<b>BACT44B0680U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0088	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 150-199, 275-276, 280-299</b>
TB0088	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0088	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0088	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
	D	A004	2	W1118	520	22		21-58-16	150-152, 275-276
	D	A004	2	W1118	523	22		25-33-11	050-099, 153-199, 277-299
	D	A004	2	W1118	523	22		21-58-16	150-152, 275-276
	D	A004	2	W1118	525	22		25-33-11	050-099, 155-199, 277-299
	D	A005	2	W1118	521	22		21-58-16	150-152, 275-276
	D	A005	2	W1118	521	22		25-33-11	153-154
	D	A005	2	W1118	523	22		25-33-11	050-099, 153-199, 277-299
	D	A005	2	W1118	523	22		21-58-16	150-152, 275-276
	D	A006	2	W0192	19A	24		21-58-16	150-199, 275-299
	D	A007	2	W1118	105	22		25-33-11	153-154
	D	A007	2	W1118	107	22		25-33-11	153-154
	D	A010	2	W0192	19B	24		21-58-16	150-199, 275-299
	D	A011	2	W0192	64K	22		28-31-21	050-099, 162-164, 276
	D	A012	2	W0192	20B	20		29-11-14	ALL
	D	A012	2	W0192	20E	20		29-11-14	ALL
	D	A013	2	W0192	63Q	24		21-58-16	050-099, 153-199, 277-299
	D	A014	2	W0192	72M	24		21-58-14	050-099, 155-199, 276-299
	D	A015	2	W0192	80N	24		21-26-11	050-099, 155-199, 276-299
	D	C001	2	W0192	03M	24		21-61-21	ALL
	D	C001	2	W0192	04X	24		21-61-21	ALL
	D	C002	2	W0192	03P	24		21-61-31	ALL
	D	C002	2	W0192	05K	24		21-61-31	ALL
	D	C003	2	W0192	516	24		21-58-16	050-099, 153-199, 277-299
	D	C003	2	W0192	522	24		21-58-16	150-152, 275-276
	D	C003	2	W0192	523	24		21-58-16	ALL
	D	C004	2	W1118	110	22		25-33-11	153-154
	D	C004	2	W1118	524	22		25-33-11	050-099, 153-199, 277-299
	D	C004	2	W1118	524	22		21-58-16	150-152, 275-276
	D	C005	2	W0192	524	22		25-33-11	050-099, 150-199, 277-299
	D	C005	2	W0192	524	22		21-58-16	275-276
	D	C006	2	W0192	19C	24		21-58-16	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 50

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0088		<b>BACT44B0680U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0088	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 150-199, 275-276, 280-299</b>
TB0088	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0088	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0088	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0088	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
	D	C007	2	W1118	109	22		25-33-11	153-154
	D	C007	2	W1118	110	22		25-33-11	153-154
	D	C010	2	W0192	19C	24		21-58-16	150-199, 275-299
	D	C010	2	W0192	19E	24		21-58-16	150-199, 275-299
	D	C011	2	W0192	64C	20		24-51-72	050-099, 162-164, 276
	D	C012	2	W0192	20C	20		29-11-14	ALL
	D	C013	2	W0192	516	24		21-58-16	050-099, 153-199, 277-299
	D	C013	2	W0192	522	24		21-58-16	050-099, 153-199, 277-299
	D	C014	2	W0192	70R	24		21-26-11	050-099, 155-199, 276-299
	D	C015	2	W0192	70R	24		21-26-11	050-099, 155-199, 276-299
	D	C015	2	W0192	70S	24		21-26-11	050-099, 155-199, 276-299
TB0090		<b>BACT44B1948U</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>D</b>	<b>DIODEBLOCK-REF284T0189-</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>F</b>	<b>BACM15C1A</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0090	<b>G</b>	<b>BACM15C1B</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>H</b>	<b>BACM15C2A</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>X</b>	<b>BACM15C3A</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0090	<b>Y</b>	<b>BACM15C3B</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>Z</b>	<b>BACM15C3C</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W0142	017	24		32-09-13	ALL
	Z	10	BJ	W0142	143	24		32-09-13	ALL
	Z	10	BJ	W0142	145	24		32-09-13	ALL
	Z	10	BJ	W0142	147	24		32-09-13	ALL
	Z	10	BJ	W0142	152	24		32-09-13	ALL
	Z	10	BJ	W0142	802	24		32-09-13	ALL
	G	15	2	W0142	031	18		27-51-11	ALL
	G	15	2	W0142	060	18		27-51-11	ALL
	G	15	2	W0142	061	22		27-51-11	ALL
	H	16	2	W0142	08P	18		30-71-21	050-099, 150-199
	H	16	2	W0142	08P	22		30-71-21	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 51

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0090		BACT44B1948U (continued)					P033-00/ /		ALL
TB0090	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0090	F	BACM15C1A (continued)					P033-00/ /		150-199, 275-299
TB0090	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0090	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0090	X	BACM15C3A (continued)					P033-00/ /		150-199, 275-299
TB0090	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0090	Z	BACM15C3C (continued)					P033-00/ /		ALL
	H	16	2	W0142	722	20		30-71-21	050-099, 155-199
	H	16	2	W0142	722	22		30-71-21	150-154, 275-299
	H	16	2	W0142	723	20		30-71-21	050-099, 155-199
	H	16	2	W0142	723	22		30-71-21	150-154, 275-278
	H	16	2	W0142	724	20		30-71-21	050-099, 150-199
	H	16	2	W0142	724	22		30-71-21	280-299
	H	16	2	W0142	725	20		30-71-21	050-099, 155-199
	H	16	2	W0142	725	22		30-71-21	150-154, 275-299
	H	16	2	W0142	726	20		30-71-21	050-099, 155-199
	H	16	2	W0142	726	22		30-71-21	150-154, 275-299
	H	16	2	W0142	727	22		30-71-21	280-299
	H	16	2	W0142	728	22		30-71-21	275-299
	H	16	2	W0142	762	22		30-71-21	275-299
	G	20	2	W0142	185	22		27-62-11	ALL
	G	20	2	W0142	865	22		27-62-11	ALL
	G	20	2	W0144	684	22		27-62-11	ALL
	Z	7	BJ	W0142	629	24		30-31-21	ALL
	Z	7	BJ	W0142	632	24		30-31-21	ALL
	Z	7	BJ	W0142	637	24		30-31-21	ALL
	Z	7	BJ	W0142	638	24		30-31-21	ALL
	Z	7	BJ	W0142	645	24		30-31-23	ALL
	Z	7	BJ	W0142	646	24		30-34-21	ALL
	Z	7	BJ	W0142	662	24		30-34-21	ALL
	Z	7	BJ	W0142	843	24		30-32-21	ALL
	Z	9	BJ	W0142	711	20		30-71-23	050-099, 155-199
	Z	9	BJ	W0142	711	22		30-71-23	150-154, 275-299
	Z	9	BJ	W0142	716	22		30-71-23	150-154, 275-299
	Z	9	BJ	W0142	716	20		30-71-23	155-199
	Z	9	BJ	W0142	740	20		30-71-23	050-099, 155-199
	Z	9	BJ	W0142	740	22		30-71-23	150-154, 275-299
	Z	9	BJ	W0142	795	20		30-71-23	050-099, 155-199
	Z	9	BJ	W0142	795	22		30-71-23	150-154, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 52

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0090		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0090	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0090	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Y	A001	BJ	W0142	592	22		30-11-11	ALL
	Y	A001	BJ	W0142	601	22		30-11-11	ALL
	Y	A001	BJ	W0142	603	22		30-11-11	ALL
	Y	A002	BJ	W0142	05R	24		21-53-21	ALL
	Y	A002	BJ	W0142	05T	24		21-53-21	ALL
	Y	A002	BJ	W0142	05W	24		21-53-21	ALL
	Y	A002	BJ	W0142	06H	24		21-53-21	ALL
	Y	A003	BJ	W0142	144	20		30-71-22	150-154
	Y	A003	BJ	W0142	733	22		30-71-22	150-154, 275
	Y	A003	BJ	W0142	763	22		30-71-22	150-154, 275
	Y	A003	BJ	W0142	828	20		SPARE	150-154
	Y	A003	BJ	W0142	828	20		30-71-22	275
	Y	A004	BJ	W0142	179	24		73-21-16	275-299
	Y	A004	BJ	W0142	180	24		73-21-16	ALL
	Y	A004	BJ	W0142	181	24		73-21-16	ALL
	Y	A004	BJ	W0142	50C	24		73-21-16	050-099, 150-199
	Y	A005	BJ	W0142	578	22		30-34-21	ALL
	Y	A005	BJ	W0142	660	22		30-34-21	ALL
	Y	A005	BJ	W0142	851	22		30-34-21	ALL
	Y	A006	BJ	W0142	09M	22		30-32-21	ALL
	Y	A006	BJ	W0142	845	22		30-32-21	ALL
	Y	A006	BJ	W0142	855	22		30-32-21	ALL
	Y	A011	BJ	W0142	583	22		30-11-11	050-099, 150-199
	Y	A011	BJ	W0142	585	22		30-11-11	275-299
	Y	A011	BJ	W0142	597	22		30-11-11	ALL
	Y	A011	BJ	W0142	599	22		30-11-11	ALL
	Y	A012	BJ	W0142	10F	22		28-22-31	ALL
	Y	A012	BJ	W0142	10K	22		28-22-31	ALL
	Y	A012	BJ	W0142	10P	22		28-22-31	ALL
	Y	A013	BJ	W0142	656	22		30-34-21	ALL
	Y	A013	BJ	W0142	659	22		30-34-21	ALL
	Y	A013	BJ	W0142	832	22		30-34-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 53

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0090		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0090	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0090	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0090	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	D	A018	2	W0142	42X	22		30-81-11	050-099, 150-199
	Y	C001	BJ	W0142	03P	22		21-44-21	ALL
	Y	C001	BJ	W0142	03S	22		21-44-21	ALL
	Y	C001	BJ	W0142	03U	22		21-44-21	ALL
	Y	C001	BJ	W0142	08F	22		21-44-21	ALL
	Y	C002	BJ	W0142	05S	24		21-53-21	ALL
	Y	C002	BJ	W0142	05X	24		21-53-21	ALL
	Y	C002	BJ	W0142	05Y	24		21-53-21	ALL
	Y	C002	BJ	W0142	06G	24		21-53-21	ALL
	Y	C003	BJ	W0142	20B	20		30-71-21	050-099, 155-199
	Y	C003	BJ	W0142	688	20		30-71-21	150-154
	Y	C003	BJ	W0142	727	20		30-71-21	050-099, 150-199
	Y	C003	BJ	W0142	728	20		30-71-21	050-099, 150-199
	Y	C003	BJ	W0142	762	20		30-71-21	050-099, 150-199
	Y	C005	BJ	W0142	668	22		30-32-21	ALL
	Y	C005	BJ	W0142	854	22		30-32-21	ALL
	Y	C005	BJ	W0142	856	22		30-32-21	ALL
	Y	C011	BJ	W0142	09L	24		30-34-21	275-299
	Y	C011	BJ	W0142	662	24		30-34-21	ALL
	Y	C011	BJ	W0142	825	24		30-34-21	050-099, 150-199
	Y	C013	BJ	W0142	148	24		32-09-13	ALL
	Y	C013	BJ	W0142	151	24		32-09-13	ALL
	Y	C013	BJ	W0142	804	24		32-09-13	ALL
	Y	C014	BJ	W0142	40U	22		30-81-11	050-099, 150-199
	Y	C014	BJ	W0142	41T	22		30-81-11	050-099, 150-199
	Y	C014	BJ	W0142	41V	22		30-81-11	050-099, 150-199
	D	C018	2	W0142	42U	22		30-11-11	050-099, 150-199
	D	C018	2	W0142	593	22		30-11-11	050-099, 150-199
	Y	DED		W0142	10FZ			28-22-31	ALL
	Y	DED		W0142	10KZ			28-22-31	ALL
	Y	DED		W0142	10PZ			28-22-31	ALL
	G	DED		W0142	185Z			27-62-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 54

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0090		BACT44B1948U (continued)					P033-00/ /		ALL
TB0090	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0090	F	BACM15C1A (continued)					P033-00/ /		150-199, 275-299
TB0090	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0090	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0090	X	BACM15C3A (continued)					P033-00/ /		150-199, 275-299
TB0090	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0090	Z	BACM15C3C (continued)					P033-00/ /		ALL
	G	DED		W0142	865Z			27-62-11	ALL
TB0092		BACT44B1948U					P033-00/ /		ALL
TB0092	F	BACM15C1A					P033-00/ /		150-199, 275-299
TB0092	G	BACM15C1B					P033-00/ /		150-199, 275-299
TB0092	H	BACM15C2A					P033-00/ /		150-199, 275-299
TB0092	X	BACM15C3A					P033-00/ /		150-199, 275-299
TB0092	Y	BACM15C3B					P033-00/ /		ALL
TB0092	Z	BACM15C3C					P033-00/ /		ALL
	Z	11	BJ	W0144	562	24		30-33-11	ALL
	Z	11	BJ	W0144	606	24		30-34-11	ALL
	Z	11	BJ	W0144	695	24		30-31-11	ALL
	Z	11	BJ	W0144	697	24		30-31-11	ALL
	Z	11	BJ	W0144	706	24		30-31-11	ALL
	Z	11	BJ	W0144	707	24		30-31-11	ALL
	Z	11	BJ	W0144	713	24		30-34-11	ALL
	Z	12	BJ	W0144	03R	24		29-11-22	ALL
	Z	12	BJ	W0144	03T	24		29-11-22	ALL
	Z	12	BJ	W0144	03U	24		29-11-22	ALL
	Z	12	BJ	W0144	04G	24		29-11-22	ALL
	Z	12	BJ	W0144	780	24		29-11-22	ALL
	Z	12	BJ	W0144	781	24		29-11-22	ALL
	Z	12	BJ	W0144	783	24		29-11-22	ALL
	Z	12	BJ	W0144	784	24		29-11-22	ALL
	Z	5	BJ	W0144	05L	24		21-53-22	ALL
	Z	5	BJ	W0144	05P	24		21-53-22	ALL
	Z	5	BJ	W0144	05V	24		21-53-22	ALL
	Z	5	BJ	W0144	05W	24		21-53-22	ALL
	Z	5	BJ	W0144	06A	24		21-53-22	ALL
	Z	5	BJ	W0144	06G	24		21-53-22	ALL
	Z	5	BJ	W0144	06K	24		21-53-22	ALL
	Z	6	BJ	W0144	05K	24		21-53-22	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 55

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0092		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0092	F	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0092	G	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0092	H	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0092	X	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0092	Y	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0092	Z	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Z	6	BJ	W0144	05R	24		21-53-22	ALL
	Z	6	BJ	W0144	05S	24		21-53-22	ALL
	Z	6	BJ	W0144	05Y	24		21-53-22	ALL
	Z	6	BJ	W0144	06C	24		21-53-22	ALL
	Z	6	BJ	W0144	06E	24		21-53-22	ALL
	Z	6	BJ	W0144	06F	24		21-53-22	ALL
	Y	A001	BJ	W0144	087	22		27-51-51	ALL
	Y	A001	BJ	W0144	092	22		27-51-51	ALL
	Y	A001	BJ	W0144	093	22		27-51-51	ALL
	Y	A002	BJ	W0144	623	22		27-62-11	ALL
	Y	A002	BJ	W0144	624	22		27-62-11	ALL
	Y	A002	BJ	W0144	626	22		27-62-11	ALL
	Y	A002	BJ	W0144	681	22		27-62-11	ALL
	Y	A003	BJ	W0144	651	22		28-22-31	ALL
	Y	A003	BJ	W0144	653	22		28-22-31	ALL
	Y	A003	BJ	W0144	654	22		28-22-31	ALL
	Y	A004	BJ	W0144	02U	22		27-62-11	ALL
	Y	A004	BJ	W0144	02V	22		27-62-11	ALL
	Y	A004	BJ	W0144	02W	22		27-62-11	ALL
	Y	A004	BJ	W0144	03J	22		27-62-11	ALL
	Y	A007	BJ	W0142	40V	22		30-81-11	050-099, 150-199
	Y	A007	BJ	W0142	41W	22		30-81-11	050-099, 150-199
	Y	A007	BJ	W0142	41X	22		30-81-11	050-099, 150-199
	Y	A007	BJ	W0144	20X	22		30-81-11	050-099, 150-199
	Y	A008	BJ	W0144	606	24		30-34-11	ALL
	Y	A008	BJ	W0144	769	24		30-34-11	ALL
	Y	A009	BJ	W0142	41P	22		30-81-11	050-099, 150-199
	Y	A009	BJ	W0144	20T	22		30-81-11	050-099, 150-199
	Y	A009	BJ	W0144	20V	22		30-81-11	050-099, 150-199
	Y	A010	BJ	W0144	068	24		27-58-11	ALL
	Y	A010	BJ	W0144	071	24		27-58-11	ALL
	Y	A010	BJ	W0144	098	24		27-58-11	ALL
	Y	C001	BJ	W0144	02C	22		27-62-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 56

Feb 06/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0092		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0092	F	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0092	G	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0092	H	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0092	X	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>150-199, 275-299</b>
TB0092	Y	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0092	Z	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Y	C001	BJ	W0144	02X	22		27-62-11	ALL
	Y	C001	BJ	W0144	03L	22		27-62-11	ALL
	Y	C001	BJ	W0144	03N	22		27-62-11	ALL
	Y	C002	BJ	W0144	04A	24		29-11-22	ALL
	Y	C002	BJ	W0144	04H	24		29-11-22	ALL
	Y	C002	BJ	W0144	04M	24		29-11-22	ALL
	Y	C003	BJ	W0144	03Q	22		29-11-22	ALL
	Y	C003	BJ	W0144	03X	22		29-11-22	ALL
	Y	C003	BJ	W0144	04E	22		29-11-22	ALL
	Y	C003	BJ	W0144	04F	22		29-11-22	ALL
	Y	C007	BJ	W0144	120	24		30-31-13	ALL
	Y	C007	BJ	W0144	536	24		30-32-11	ALL
	Y	C007	BJ	W0144	706	24		30-31-11	ALL
	Y	C007	BJ	W0144	714	24		30-31-11	ALL
	Y	C009	BJ	W0144	033	24		27-58-11	ALL
	Y	C009	BJ	W0144	069	24		27-58-11	ALL
	Y	C009	BJ	W0144	099	24		27-58-11	ALL
	Y	C010	BJ	W0144	067	24		27-58-11	ALL
	Y	C010	BJ	W0144	070	24		27-58-11	ALL
	Y	C010	BJ	W0144	095	24		27-58-11	ALL
	Y	DED		W0144	651Z			28-22-31	ALL
	Y	DED		W0144	653Z			28-22-31	ALL
	Y	DED		W0144	654Z			28-22-31	ALL
TB0096		<b>BACT442150U</b>					<b>P061-00/ /</b>		<b>051-099, 150-199, 275-299</b>
TB0096	D	<b>DIODEBLOCK-REF284T3000-</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	F	<b>BACM15C1A</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	G	<b>BACM15C1B</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	X	<b>BACM15C3A</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	Y	<b>BACM15C3B</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	Z	<b>BACM15C3C</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
	G	16	2	W0070	12E	18		25-63-11	ALL
	G	16	2	W0070	12F	18		25-63-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 57

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0096		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>051-099, 150-199, 275-299</b>
TB0096	<b>D</b>	<b>DIODEBLOCK-REF284T3000- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
	G	16	2	W0070	852	20		25-63-11	ALL
	G	17	2	W0066	04C	22		25-65-12	ALL
	G	17	2	W0066	58W	18		33-51-11	ALL
	G	17	2	W0066	58X	18		33-51-11	ALL
	G	18	2	W0066	55H	18		27-81-21	ALL
	G	18	2	W0066	55J	18		27-81-21	ALL
	G	18	2	W0066	55K	18		27-81-21	ALL
	G	19	2	W0066	55E	18		27-81-11	ALL
	G	19	2	W0066	55F	18		27-81-11	ALL
	G	19	2	W0066	55G	18		27-81-11	ALL
	G	20	2	W0066	53X	18		27-51-11	ALL
	G	20	2	W0066	53Y	18		27-51-11	ALL
	G	20	2	W0066	53Z	18		27-51-11	ALL
	G	21	2	W0066	08G	16		33-11-14	ALL
	G	21	2	W0070	05F	16		33-11-14	ALL
	G	21	2	W0070	05G	16		33-11-14	ALL
	G	21	2	W0070	05H	16		33-11-14	ALL
	G	30	2	W0062	80A	18		33-13-21	ALL
	G	30	2	W0062	81D	18		33-13-21	ALL
	G	30	2	W0066	10H	18		33-13-21	ALL
	X	A001	BJ	W0060	053	24		24-22-41	ALL
	X	A001	BJ	W0062	822	24		24-22-41	ALL
	X	A002	BJ	W0060	103	24		24-22-41	ALL
	X	A002	BJ	W0062	64C	24		24-22-41	ALL
	X	A003	BJ	W0062	338B	24		21-61-61	ALL
	X	A003	BJ	W0066	338B	24		21-61-61	ALL
	X	A004	BJ	W0060	032	24		49-72-11	ALL
	X	A004	BJ	W0070	032	24		49-72-11	ALL
	D	A005	2	W0060	013	24		24-27-41	050-099, 150-199, 275-278
	D	A005	2	W0060	105	24		24-27-41	ALL
	X	A009	BJ	W0060	016	22		49-61-11	ALL
	X	A009	BJ	W0070	07C	22		49-61-11	ALL
	X	A010	BJ	W0060	101	20		24-22-41	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 58

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0096		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>051-099, 150-199, 275-299</b>
TB0096	<b>D</b>	<b>DIODEBLOCK-REF284T3000- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
	X	A010	BJ	W0070	01S	20		24-22-41	ALL
	Y	A011	BJ	W0060	021	22		49-61-11	ALL
	Y	A011	BJ	W0060	113	22		49-61-11	ALL
	Y	A011	BJ	W0070	07B	22		49-61-11	ALL
	D	A013	2	W0070	788R	22		26-15-11	ALL
	D	A014	2	W0070	789R	22		26-15-11	ALL
	F	A015	2	W0062	645	16		33-11-14	ALL
	F	A015	2	W0070	645	16		33-11-14	ALL
	D	A024	2	W0070	785R	22		26-11-21	ALL
	D	A025	2	W0070	775R	22		26-11-21	ALL
	D	A026	2	W0070	776R	22		26-11-21	ALL
	D	A027	2	W0070	782R	22		26-11-11	ALL
	D	A028	2	W0070	765R	22		26-11-11	ALL
	D	A029	2	W0070	766R	22		26-11-11	ALL
	D	A033	2	W0062	708	22		28-31-12	050-099, 155-199, 277-299
	X	B003	BJ	W0062	338R	24		21-61-61	ALL
	X	B003	BJ	W0066	338R	24		21-61-61	ALL
	X	B004	BJ	W0060	026	24		49-72-11	ALL
	X	B004	BJ	W0070	033	24		49-72-11	ALL
	X	B009	BJ	W0060	018	22		49-61-11	ALL
	X	B009	BJ	W0070	725	22		49-61-11	ALL
	X	B010	BJ	W0060	054	24		24-22-41	ALL
	X	B010	BJ	W0070	01R	24		24-22-41	ALL
	X	C001	BJ	W0060	108	24		24-41-11	ALL
	X	C001	BJ	W0066	677	24		24-41-11	ALL
	X	C002	BJ	W0060	112	24		24-41-12	ALL
	X	C002	BJ	W0066	670	24		24-41-12	ALL
	X	C003	BJ	W0062	338Y	24		21-61-61	ALL
	X	C003	BJ	W0066	338Y	24		21-61-61	ALL
	X	C004	BJ	W0060	114	20		24-32-41	275-299
	X	C004	BJ	W0066	72A	20		24-32-41	275-299
	D	C005	2	W0060	104	24		24-22-41	ALL
	D	C005	2	W0062	64D	24		24-22-41	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0000

Page 59

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0096		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>051-099, 150-199, 275-299</b>
TB0096	<b>D</b>	<b>DIODEBLOCK-REF284T3000- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0096	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
	X	C010	BJ	W0060	102	24		24-22-41	ALL
	X	C010	BJ	W0070	01P	24		24-22-41	ALL
	D	C013	2	W0070	790R	22		26-15-11	ALL
	D	C013	2	W0070	791R	22		26-15-11	ALL
	D	C014	2	W0070	791R	22		26-15-11	ALL
	D	C024	2	W0070	777R	22		26-11-21	ALL
	D	C024	2	W0070	786R	22		26-11-21	ALL
	D	C025	2	W0070	786R	22		26-11-21	ALL
	D	C025	2	W0070	787R	22		26-11-21	ALL
	D	C026	2	W0070	787R	22		26-11-21	ALL
	D	C027	2	W0070	767R	22		26-11-11	ALL
	D	C027	2	W0070	783R	22		26-11-11	ALL
	D	C028	2	W0070	783R	22		26-11-11	ALL
	D	C028	2	W0070	784R	22		26-11-11	ALL
	D	C029	2	W0070	784R	22		26-11-11	ALL
	D	C033	2	W0070	744	22		28-31-12	050-099, 155-199, 277-299
	X	D001	BJ	W0060	109	24		24-41-11	ALL
	X	D001	BJ	W0066	676	24		24-41-11	ALL
	X	D002	BJ	W0060	110	20		24-41-11	ALL
	X	D002	BJ	W0066	53F	20		24-41-11	ALL
	X	D004	BJ	W0060	025	24		49-72-11	050-099, 162-199, 275-299
	X	D004	BJ	W0066	32A	24		49-72-11	050-099, 162-199, 275-299
	X	D009	BJ	W0060	111	20		24-41-11	ALL
	X	D009	BJ	W0070	02M	20		24-41-11	ALL
	X	D010	BJ	W0060	107	24		24-41-11	ALL
	X	D010	BJ	W0070	02N	24		24-41-11	ALL
	X	DED		W0060	110Z			24-41-11	ALL
	X	DED		W0060	111Z			24-41-11	ALL
	D	DED		W0062	708Z			28-31-12	050-099, 155-199, 277-299
	X	DED		W0070	032Z			49-72-11	ALL
	X	DED		W0070	033Z			49-72-11	ALL
	Y	DED		W0070	07BZ			49-61-11	ALL
	X	DED		W0070	07CZ			49-61-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 60

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0096		BACT442150U (continued)					P061-00/ /		051-099, 150-199, 275-299
TB0096	D	DIODEBLOCK-REF284T3000- (continued)					P061-00/ /		ALL
TB0096	F	BACM15C1A (continued)					P061-00/ /		ALL
TB0096	G	BACM15C1B (continued)					P061-00/ /		ALL
TB0096	X	BACM15C3A (continued)					P061-00/ /		ALL
TB0096	Y	BACM15C3B (continued)					P061-00/ /		ALL
TB0096	Z	BACM15C3C (continued)					P061-00/ /		150-199, 275-299
	D	DED		W0070	744Z			28-31-12	050-099, 155-199, 277-299
TB0098		BACT442150U					P061-00/ /		150-199, 275-299
TB0098	X	BACM15C3A					P061-00/ /		ALL
TB0098	Y	BACM15C3B					P061-00/ /		ALL
TB0098	Z	BACM15C3C					P061-00/ /		ALL
	X			W0062	239	20		23-22-15	050-099
	X			W0062	239Z			23-22-15	050-099
	X			W0065	226	20		23-22-15	150-199
	X			W0065	226Z			23-22-15	150-199
	Z	37	BJ	W0062	021	22		33-16-26	ALL
	Z	37	BJ	W0062	60R	22		33-16-22	ALL
	Z	37	BJ	W0065	023	22		33-16-26	ALL
	Z	38	BJ	W0062	019	22		33-16-26	ALL
	Z	38	BJ	W0062	60S	22		33-16-22	ALL
	Z	38	BJ	W0062	60W	22		33-16-22	ALL
	Z	38	BJ	W0062	804	22		33-16-26	ALL
	Z	38	BJ	W0062	824	22		33-16-26	ALL
	Z	38	BJ	W0062	874	22		33-16-26	ALL
	Z	38	BJ	W0065	024	22		33-16-26	ALL
	X	A002	BJ	W0062	099	22		31-31-26	ALL
	X	A002	BJ	W0070	101	22		31-31-26	ALL
	X	A003	BJ	W0062	101	20		78-34-11	ALL
	X	A003	BJ	W0070	63G	20		78-34-11	ALL
	X	A004	BJ	W0062	668	24		24-22-11	ALL
	X	A004	BJ	W0070	12A	24		24-22-11	ALL
	X	A006	BJ	W0062	787R	22		26-18-31	ALL
	X	A006	BJ	W0070	800R	22		26-18-31	ALL
	X	A008	BJ	W0062	66P	24		33-11-13	ALL
	X	A008	BJ	W0070	05D	24		33-11-13	ALL
	Y	A011	BJ	W0062	144	22		21-58-11	ALL
	Y	A011	BJ	W0070	13M	24		21-58-16	ALL
	Y	A011	BJ	W0070	13N	22		21-58-16	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 61

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0098		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0098	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0098	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0098	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
Y		A012	BJ	W0062	62F	22		74-31-11	ALL
Y		A012	BJ	W0062	62G	22		74-31-11	ALL
Y		A012	BJ	W0070	106	22		74-31-11	ALL
Y		A012	BJ	W0070	107	22		74-31-11	ALL
Y		A013	BJ	W0062	039	22		29-11-11	ALL
Y		A013	BJ	W0062	55P	22		29-11-11	ALL
Y		A013	BJ	W0070	03R	22		29-11-11	ALL
Y		A014	BJ	W0062	123	24		21-26-31	ALL
Y		A014	BJ	W0062	50D	24		21-25-11	ALL
Y		A014	BJ	W0070	01A	24		21-25-11	ALL
Y		A014	BJ	W0070	01B	24		21-25-11	ALL
Y		A015	BJ	W0065	301R	24		31-31-19	ALL
Y		A015	BJ	W0070	301R	22		21-31-31	ALL
Y		A015	BJ	W0070	305R	22		21-31-31	ALL
Y		A016	BJ	W0065	301Y	24		31-31-19	ALL
Y		A016	BJ	W0070	301Y	22		21-31-31	ALL
Y		A016	BJ	W0070	305Y	22		21-31-31	ALL
X		A022	BJ	W0062	239R	24		23-22-15	ALL
X		A022	BJ	W0065	226R	24		23-22-15	ALL
Y		A028	BJ	W0062	63B	24		78-36-11	ALL
Y		A028	BJ	W0062	63W	20		78-34-11	ALL
Y		A028	BJ	W0062	714	24		78-36-11	ALL
Y		A033	BJ	W0062	59Y	22		33-16-12	ALL
Y		A033	BJ	W0062	59Z	22		33-16-12	ALL
Y		A033	BJ	W0062	60B	22		33-16-12	ALL
Y		A035	BJ	W0062	60K	22		33-16-22	ALL
Y		A035	BJ	W0062	823	22		33-16-26	ALL
X		B004	BJ	W0062	54A	24		24-22-11	ALL
X		B004	BJ	W0070	12B	24		24-22-11	ALL
X		B006	BJ	W0062	62Y	24		78-34-11	ALL
X		B006	BJ	W0070	08V	24		78-34-11	ALL
X		B008	BJ	W0062	66R	24		33-11-13	ALL
X		B008	BJ	W0070	14D	24		33-11-13	ALL
X		B022	BJ	W0062	239B	24		23-22-15	ALL
X		B022	BJ	W0065	226B	24		23-22-15	ALL
X		C004	BJ	W0062	61G	22		36-11-51	ALL
X		C004	BJ	W0070	06U	22		36-11-51	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 62

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0098		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0098	X	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0098	Y	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0098	Z	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	X	C006	BJ	W0062	62H	22		74-31-11	ALL
	X	C006	BJ	W0070	108	22		74-31-11	ALL
	X	C008	BJ	W0062	102	24		73-21-15	ALL
	X	C008	BJ	W0070	15A	24		73-21-15	ALL
	Y	C011	BJ	W0062	04K	22		29-33-11	ALL
	Y	C011	BJ	W0062	883	22		29-21-32	ALL
	Y	C011	BJ	W0070	024	22		29-33-11	ALL
	Y	C012	BJ	W0062	62W	24		78-34-11	ALL
	Y	C012	BJ	W0062	62X	24		78-34-11	ALL
	Y	C012	BJ	W0070	08U	24		78-34-11	ALL
	Y	C012	BJ	W0070	63N	20		78-34-11	ALL
	Y	C013	BJ	W0062	038	22		29-11-11	ALL
	Y	C013	BJ	W0062	55R	22		29-11-11	ALL
	Y	C013	BJ	W0070	03P	22		29-11-11	ALL
	Y	C015	BJ	W0065	301B	24		31-31-19	ALL
	Y	C015	BJ	W0070	301B	22		21-31-31	ALL
	Y	C015	BJ	W0070	305B	22		21-31-31	ALL
	Y	C016	BJ	W0070	123	20		78-34-11	ALL
	Y	C016	BJ	W0070	126	20		78-34-11	ALL
	Y	C016	BJ	W0070	127	20		78-34-11	ALL
	Y	C033	BJ	W0062	60F	22		33-16-12	ALL
	Y	C033	BJ	W0062	63M	24		33-16-14	ALL
	Y	C035	BJ	W0062	60M	22		33-16-22	ALL
	Y	C035	BJ	W0062	803	22		33-16-26	ALL
	Y	C035	BJ	W0062	873	22		33-16-26	ALL
	X	CAP	Y	W0062	50R	24		SPARE	051-099, 150-154
	X	CAP	Y	W0070	01L	24		SPARE	051-099, 150-154
	X	D004	BJ	W0062	081	24		36-11-51	ALL
	X	D004	BJ	W0070	06V	24		36-11-51	ALL
	X	D006	BJ	W0062	62J	24		74-31-11	ALL
	X	D006	BJ	W0070	109	24		74-31-11	ALL
	X	D008	BJ	W0062	50R	24		21-44-21	275-276
	X	D008	BJ	W0070	01L	24		21-44-21	275-276
	X	D022	BJ	W0062	537	24		23-22-15	ALL
	X	D022	BJ	W0065	061	24		23-22-15	ALL
	X	DED		W0062	101Z			78-34-11	ALL
	Y	DED		W0062	144Z			21-58-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 63

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0098		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0098	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0098	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0098	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	DED		W0062	59YZ			33-16-12	ALL
	Y	DED		W0062	59ZZ			33-16-12	ALL
	Y	DED		W0062	60BZ			33-16-12	ALL
	Y	DED		W0062	60MZ			33-16-22	ALL
	Z	DED		W0062	60RZ			33-16-22	ALL
	Y	DED		W0062	62FZ			74-31-11	ALL
	Y	DED		W0062	62GZ			74-31-11	ALL
	X	DED		W0062	62HZ			74-31-11	ALL
	Y	DED		W0062	803Z			33-16-26	ALL
	Z	DED		W0065	023Z			33-16-26	ALL
	Z	DED		W0065	024Z			33-16-26	ALL
	Y	DED		W0065	301Z			31-31-19	ALL
	Y	DED		W0070	024Z			29-33-11	ALL
	Y	DED		W0070	03PZ			29-11-11	ALL
	Y	DED		W0070	03RZ			29-11-11	ALL
	Y	DED		W0070	08UZ			78-34-11	ALL
	X	DED		W0070	08VZ			78-34-11	ALL
	X	DED		W0070	101Z			31-31-26	ALL
	Y	DED		W0070	123Z			78-34-11	ALL
	Y	DED		W0070	126Z			78-34-11	ALL
	Y	DED		W0070	127Z			78-34-11	ALL
	X	DED		W0070	63GZ			78-34-11	ALL
	Y	DED		W0070	63NZ			78-34-11	ALL
	X	REF		W0062	239	20		23-22-15	150-199, 275-299
	X	REF		W0062	239Z			23-22-15	150-199, 275-299
	X	REF		W0065	226	20		23-22-15	050-099, 275-299
	X	REF		W0065	226Z			23-22-15	050-099, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0000

Page 64 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0100		BACT442150U					P061-00/ /		150-199, 275-299
TB0100	D	DIODEBLOCK-REF287T4163-					P061-00/ /		ALL
TB0100	F	BACM15C1A					P061-00/ /		155-157, 164-199, 277-299
TB0100	G	BACM15C1B					P061-00/ /		ALL
TB0100	X	BACM15C3A					P061-00/ /		ALL
TB0100	Y	BACM15C3B					P061-00/ /		ALL
TB0100	Z	BACM15C3C					P061-00/ /		ALL
	Z	19	BJ	W0062	59S	24		33-14-31	ALL
	Z	19	BJ	W0062	59T	24		33-14-31	ALL
	Z	19	BJ	W0066	59S	24		33-14-31	ALL
	Z	20	BJ	W0062	142	22		21-33-11	ALL
	Z	20	BJ	W0062	50L	24		21-33-11	ALL
	Z	20	BJ	W0062	50M	22		21-33-11	ALL
	Z	20	BJ	W0062	63J	24		31-51-31	ALL
	Z	20	BJ	W0066	50M	22		21-33-11	ALL
	Z	21	BJ	W0062	17J	24		31-41-13	ALL
	Z	21	BJ	W0062	17L	24		31-41-13	ALL
	Z	21	BJ	W0062	17N	24		31-41-13	ALL
	Z	21	BJ	W0062	63H	24		31-41-13	ALL
	Z	21	BJ	W0066	63H	24		31-41-13	ALL
	Z	22	BJ	W0062	17R	24		31-41-13	ALL
	Z	22	BJ	W0062	17T	24		31-41-13	ALL
	Z	22	BJ	W0062	18F	24		31-41-13	ALL
	Z	22	BJ	W0062	18J	24		31-41-13	ALL
	Z	22	BJ	W0062	18M	24		31-41-13	ALL
	Z	22	BJ	W0062	63H	24		31-41-13	ALL
	G	41	2	W0062	67P	16		25-31-31	277-299
	G	41	2	W0062	67R	16		25-31-31	277-299
	G	41	2	W0062	699	16		25-31-31	277-299
	G	42	2	W0062	657	16		25-31-21	050-099, 275-299
	G	42	2	W0062	657	20		25-31-21	150-199
	G	42	2	W0062	65D	20		25-31-21	050-099, 150-199
	G	42	2	W0062	65D	18		25-31-21	275-299
	G	42	2	W0062	65E	16		25-31-21	ALL
	X	A001	BJ	W0062	51Z	24		21-51-11	ALL
	X	A001	BJ	W0066	79W	24		21-51-11	050-099, 150-199
	X	A001	BJ	W0066	889	24		21-51-11	275-299
	X	A002	BJ	W0062	208B	20		21-65-11	ALL
	X	A002	BJ	W0066	208B	20		21-65-11	ALL
	X	A003	BJ	W0062	208R	20		21-65-11	ALL
	X	A003	BJ	W0066	208R	20		21-65-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 1

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0100		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0100	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>155-157, 164-199, 277-299</b>
TB0100	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	X	A004	BJ	W0062	674	24		24-51-71	ALL
	X	A004	BJ	W0066	63K	24		24-51-71	ALL
	D	A009	2	W0062	173R	22		26-18-11	050-099, 162-199
	D	A009	2	W0062	405R	22		26-18-11	150-157, 275-299
	D	A009	2	W0062	406R	22		26-18-12	050-099, 162-199
	D	A010	2	W0062	174R	22		26-18-21	150-157, 275-299
	D	A010	2	W0066	086R	22		26-18-21	050-099, 162-199
	D	A010	2	W0066	410R	22		26-18-22	050-099, 162-199
	Y	A011	BJ	W0062	174R	22		26-18-21	150-157, 275-299
	Y	A011	BJ	W0066	086R	22		26-18-21	150-157, 275-299
	Y	A011	BJ	W0066	410R	22		26-18-22	150-157, 275-299
	Y	A012	BJ	W0062	55Y	22		28-41-13	ALL
	Y	A012	BJ	W0062	55Z	22		28-41-13	050-099, 150-156, 162-166, 275-276
	Y	A012	BJ	W0062	67G	22		28-41-13	157, 167-199, 277-299
	Y	A012	BJ	W0066	622	22		28-41-13	ALL
	Y	A013	BJ	W0062	52C	24		27-18-11	ALL
	Y	A013	BJ	W0062	52D	24		27-18-11	ALL
	Y	A013	BJ	W0066	64B	24		27-18-11	ALL
	Y	A016	BJ	W0062	055	20		21-31-21	ALL
	Y	A016	BJ	W0062	50K	20		21-31-21	ALL
	Y	A016	BJ	W0066	50F	20		21-31-21	ALL
	Y	A026	BJ	W0062	572	22		74-31-11	ALL
	Y	A026	BJ	W0062	62D	22		74-31-11	ALL
	Y	A028	BJ	W0062	639	20		28-31-11	050-099, 155-199, 276-299
	Y	A028	BJ	W0062	700	20		28-31-11	050-099, 155-199, 276-299
	Y	A028	BJ	W0062	707	20		28-31-11	050-099, 155-199, 276-299
	Y	A029	BJ	W0062	006	22		29-32-11	ALL
	Y	A029	BJ	W0062	55T	22		29-32-11	ALL
	Y	A029	BJ	W0062	55U	22		29-32-11	ALL
	Y	A030	BJ	W0062	04G	22		29-21-32	ALL
	Y	A030	BJ	W0062	881	22		29-21-32	ALL
	Y	A030	BJ	W0062	889	22		29-21-32	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 2

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0100		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0100	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>155-157, 164-199, 277-299</b>
TB0100	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	A031	BJ	W0062	017	22		29-11-31	ALL
	Y	A031	BJ	W0062	04F	22		29-21-32	ALL
	Y	A031	BJ	W0062	887	22		29-11-31	ALL
	Y	A032	BJ	W0062	52N	24		27-58-11	ALL
	Y	A032	BJ	W0062	52P	24		27-58-11	ALL
	Y	A032	BJ	W0062	52R	24		27-58-11	ALL
	Y	A033	BJ	W0062	53V	22		27-13-11	ALL
	Y	A033	BJ	W0062	53W	22		27-13-11	ALL
	Y	A033	BJ	W0062	802	22		27-13-11	ALL
	Y	A034	BJ	W0062	51W	24		24-11-11	ALL
	Y	A034	BJ	W0062	51X	24		24-11-11	ALL
	Y	A034	BJ	W0062	51Y	24		24-11-11	ALL
	Y	A034	BJ	W0062	830	24		24-11-11	ALL
	F	A035	2	W0062	70W	18		38-32-11	156-157, 166-199, 277-299
	F	A035	2	W0066	61N	18		38-32-11	156
	F	A035	2	W0066	61X	18		38-32-11	157, 166-199, 277-299
	Y	A037	BJ	W0062	506	22		21-24-11	050-099, 150-199
	Y	A037	BJ	W0062	66F	22		21-24-11	050-099, 150-199
	Y	A037	BJ	W0062	66G	24		21-24-11	050-099, 150-199
	Y	A039	BJ	W0062	056	20		21-31-11	ALL
	Y	A039	BJ	W0062	50H	20		21-31-11	ALL
	Y	A039	BJ	W0062	50J	20		21-31-11	ALL
	Y	A040	BJ	W0062	50B	22		21-25-11	ALL
	Y	A040	BJ	W0062	50C	22		21-25-11	ALL
	Y	A040	BJ	W0062	517	22		21-25-11	ALL
	X	C005	BJ	W0062	230B	24		28-41-13	ALL
	X	C005	BJ	W0066	230B	24		28-41-13	ALL
	X	C006	BJ	W0062	01L	24		28-43-11	ALL
	X	C006	BJ	W0066	775	24		28-43-11	ALL
	X	C008	BJ	W0062	100	24		73-21-15	ALL
	X	C008	BJ	W0066	15A	24		73-21-15	ALL
	D	C009	2	W0062	106R	22		26-18-11	ALL
	D	C010	2	W0062	105R	22		26-18-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 3

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0100		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0100	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>155-157, 164-199, 277-299</b>
TB0100	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	C011	BJ	W0062	509	20		24-51-72	050-099, 162-164, 276
	Y	C011	BJ	W0062	521	20		24-51-72	050-099, 162-164, 276
	Y	C011	BJ	W0066	501	20		24-51-72	050-099, 162-164, 276
	Y	C013	BJ	W0062	649	24		33-16-11	ALL
	Y	C013	BJ	W0062	650	24		33-16-11	ALL
	Y	C013	BJ	W0066	82G	24		33-16-11	ALL
	Y	C014	BJ	W0062	56A	24		30-41-11	ALL
	Y	C014	BJ	W0062	56B	24		30-41-11	ALL
	Y	C014	BJ	W0066	56U	24		30-41-12	ALL
	Y	C015	BJ	W0062	124	24		21-28-11	ALL
	Y	C015	BJ	W0062	128	24		21-28-11	ALL
	Y	C015	BJ	W0066	179	24		21-61-81	ALL
	Y	C016	BJ	W0062	023	24		24-51-71	ALL
	Y	C016	BJ	W0062	53P	24		24-51-71	ALL
	Y	C016	BJ	W0066	002	24		24-51-71	ALL
	Y	C016	BJ	W0066	023	24		24-51-71	ALL
	Y	C025	BJ	W0062	024	22		29-33-11	ALL
	Y	C025	BJ	W0062	70B	20		29-11-14	ALL
	Y	C025	BJ	W0062	858	22		29-33-11	ALL
	Y	C027	BJ	W0062	54H	24		SPARE	152, 154, 156, 162, 166-199
	Y	C027	BJ	W0062	54J	24		SPARE	152, 154, 156, 162, 166-199
	Y	C027	BJ	W0062	637	24		SPARE	152, 154, 156, 162, 166-199
	Y	C028	BJ	W0062	636	22		28-31-11	050-099, 155-199, 276-299
	Y	C028	BJ	W0062	688	22		28-31-11	050-099, 155-199, 276-299
	Y	C028	BJ	W0062	695	22		28-31-11	050-099, 155-199, 276-299
	Y	C029	BJ	W0062	015	22		29-32-11	ALL
	Y	C029	BJ	W0062	55V	22		29-32-11	ALL
	Y	C029	BJ	W0062	55W	22		29-32-11	ALL
	Y	C030	BJ	W0062	005	22		29-21-32	ALL
	Y	C030	BJ	W0062	018	22		29-11-31	ALL
	Y	C030	BJ	W0062	05S	22		29-11-31	ALL
	Y	C030	BJ	W0062	05T	22		29-11-31	ALL
	Y	C031	BJ	W0062	04D	22		29-21-32	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 4

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0100		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0100	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>155-157, 164-199, 277-299</b>
TB0100	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	C031	BJ	W0062	877	22		29-21-32	ALL
	Y	C032	BJ	W0062	52S	24		27-58-11	ALL
	Y	C032	BJ	W0062	52T	24		27-58-11	ALL
	Y	C032	BJ	W0062	52U	24		27-58-11	ALL
	Y	C033	BJ	W0062	52B	24		27-18-11	ALL
	Y	C033	BJ	W0062	52E	24		27-18-11	ALL
	Y	C033	BJ	W0062	52F	24		27-18-11	ALL
	Y	C034	BJ	W0062	53J	24		24-51-71	ALL
	Y	C034	BJ	W0062	53K	24		24-51-71	ALL
	Y	C034	BJ	W0062	53L	24		24-51-71	ALL
	Y	C034	BJ	W0066	53R	24		24-51-71	ALL
	F	C035	2	W0062	70X	18		38-32-11	156-157, 166-199, 277-299
	F	C035	2	W0066	65X	18		38-32-11	156-157, 166-199, 277-299
	Y	C039	BJ	W0062	51A	24		21-53-22	ALL
	Y	C039	BJ	W0062	51B	24		21-53-22	ALL
	Y	C039	BJ	W0062	51C	24		21-53-22	ALL
	Y	C040	BJ	W0062	50E	24		21-26-11	ALL
	Y	C040	BJ	W0062	50G	24		21-26-11	ALL
	Y	CAP	Y	W0062	571	22		SPARE	ALL
	Y	CAP	Y	W0062	62E	22		SPARE	ALL
	X	D002	BJ	W0062	206B	20		21-65-11	ALL
	X	D002	BJ	W0066	213B	20		21-65-11	ALL
	X	D003	BJ	W0062	206R	20		21-65-11	ALL
	X	D003	BJ	W0066	213R	20		21-65-11	ALL
	X	D005	BJ	W0062	230R	24		28-41-13	ALL
	X	D005	BJ	W0066	230R	24		28-41-13	ALL
	X	D006	BJ	W0062	313R	24		33-13-18	ALL
	X	D006	BJ	W0066	313R	24		33-13-18	ALL
	X	D007	BJ	W0062	313B	24		33-13-18	ALL
	X	D007	BJ	W0066	313B	24		33-13-18	ALL
	X	D008	BJ	W0062	313Y	24		33-13-18	ALL
	X	D008	BJ	W0066	313Y	24		33-13-18	ALL
	Y	DED		W0062	006Z			29-32-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 5

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0100		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0100	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>155-157, 164-199, 277-299</b>
TB0100	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0100	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	DED		W0062	015Z			29-32-11	ALL
	Y	DED		W0062	017Z			29-11-31	ALL
	Z	DED		W0062	142Z			21-33-11	ALL
	Y	DED		W0062	53VZ			27-13-11	ALL
	Y	DED		W0062	53WZ			27-13-11	ALL
	Y	DED		W0062	55TZ			29-32-11	ALL
	Y	DED		W0062	55UZ			29-32-11	ALL
	Y	DED		W0062	55VZ			29-32-11	ALL
	Y	DED		W0062	55WZ			29-32-11	ALL
	Y	DED		W0062	636Z			28-31-11	050-099, 155-199, 276-299
	Y	DED		W0062	688Z			28-31-11	050-099, 155-199, 276-299
	Y	DED		W0062	695Z			28-31-11	050-099, 155-199, 276-299
	Y	DED		W0062	802Z			27-13-11	ALL
	Y	DED		W0062	887Z			29-11-31	ALL
	Z	DED		W0066	50MZ			21-33-11	ALL
	X	DED		W0066	889Z			21-51-11	275-299
<b>TB0101</b>		<b>284T0384</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
<b>TB0101</b>	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
<b>TB0101</b>	<b>H</b>	<b>BACM15C2A</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
	G			W0101	218Z			22-21-11	ALL
	G			W0101	220Z			27-11-12	ALL
	G			W0101	222Z			27-11-12	ALL
	G			W0111	217Z			22-21-11	ALL
	G			W0111	221Z			27-11-12	ALL
	G			W0111	222Z			27-11-12	ALL
	G			W0121	212Z			22-21-11	ALL
	G			W0121	214Z			22-21-11	ALL
	G			W0121	215Z			22-21-11	ALL
	G			W0121	216Z			22-22-11	ALL
	G			W0121	217Z			22-22-11	ALL
	G			W0121	218Z			22-22-11	ALL
	G	10	2	W0101	302B	22		27-61-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 6

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		<b>284T0384 (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
	G	10	2	W0101	306B	22		27-61-15	ALL
	G	10	2	W0101	308B	22		27-61-16	ALL
	G	10	2	W0101	312B	22		27-61-15	ALL
	G	101	2	W0101	133	22		22-24-11	ALL
	G	101	2	W0101	134	22		22-24-11	ALL
	G	101	2	W0101	135	22		22-24-11	ALL
	G	102	2	W0101	017	22		27-41-11	150-154
	G	102	2	W0101	018	22		27-41-31	050-099, 155-199, 275-299
	G	102	2	W0101	018	22		27-41-11	150-154
	G	102	2	W0101	146	22		27-41-11	150-154
	G	102	2	W0101	837	24		31-31-15	050-099, 155-199, 275-299
	G	102	2	W0121	163	22		27-41-31	050-099, 155-199, 275-299
	G	102	2	W1101	123	22		27-41-31	050-099, 155-199, 275-299
	H	103	2	W0101	070	22		27-09-12	ALL
	H	103	2	W0101	071	22		27-09-12	ALL
	H	103	2	W0101	072	22		27-09-12	ALL
	H	103	2	W0101	073	22		27-09-12	ALL
	H	103	2	W0101	074	22		27-09-12	ALL
	H	103	2	W0101	075	22		27-09-12	ALL
	H	103	2	W0101	076	22		27-09-12	ALL
	H	103	2	W0101	077	22		27-09-12	ALL
	G	105	2	W0101	079	22		27-09-13	ALL
	G	105	2	W0101	081	22		27-09-13	ALL
	G	105	2	W0101	083	22		27-09-13	ALL
	G	106	2	W0101	078	22		27-09-13	ALL
	G	106	2	W0101	080	22		27-09-13	ALL
	G	106	2	W0101	082	22		27-09-13	ALL
	G	107	2	W0101	149	22		27-41-11	ALL
	G	107	2	W0101	156	22		27-41-11	ALL
	G	107	2	W0101	168	22		27-41-11	ALL
	G	107	2	W0101	70L	20		29-11-14	ALL
	H	108	2	W0101	110	22		27-61-11	ALL
	H	108	2	W0101	111	22		27-61-11	ALL
	H	108	2	W0101	112	22		27-61-11	ALL
	H	108	2	W0101	113	22		27-61-11	ALL
	H	108	2	W0101	114	22		27-61-11	ALL
	G	11	2	W0101	302Y	22		27-61-14	ALL
	G	11	2	W0101	306Y	22		27-61-15	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 7

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		284T0384 (continued)					SHELF/E01/01		ALL
TB0101	G	BACM15C1B (continued)					SHELF/E01/01		ALL
TB0101	H	BACM15C2A (continued)					SHELF/E01/01		ALL
	G	11	2	W0101	308Y	22		27-61-16	ALL
	G	11	2	W0101	312Y	22		27-61-15	ALL
	G	110	2	W0101	303R	22		27-61-14	ALL
	G	110	2	W0101	307R	22		27-61-15	ALL
	G	110	2	W0101	309R	22		27-61-16	ALL
	G	110	2	W0101	313R	22		27-61-15	ALL
	G	111	2	W0101	303B	22		27-61-14	ALL
	G	111	2	W0101	307B	22		27-61-15	ALL
	G	111	2	W0101	309B	22		27-61-16	ALL
	G	111	2	W0101	313B	22		27-61-15	ALL
	G	112	2	W0101	303Y	22		27-61-14	ALL
	G	112	2	W0101	307Y	22		27-61-15	ALL
	G	112	2	W0101	309Y	22		27-61-16	ALL
	G	112	2	W0101	313Y	22		27-61-15	ALL
	H	113	2	W0101	211R	22		27-61-14	ALL
	H	113	2	W0101	212R	22		27-61-15	ALL
	H	113	2	W0101	213R	22		27-61-15	ALL
	H	113	2	W0101	214R	22		27-61-15	ALL
	H	113	2	W0101	215R	22		27-61-15	ALL
	H	113	2	W0101	216R	22		27-61-16	ALL
	H	115	2	W0101	052	22		27-61-15	ALL
	H	115	2	W0101	211B	22		27-61-14	ALL
	H	115	2	W0101	212B	22		27-61-15	ALL
	H	115	2	W0101	213B	22		27-61-15	ALL
	H	115	2	W0101	214B	22		27-61-15	ALL
	H	115	2	W0101	215B	22		27-61-15	ALL
	H	115	2	W0101	216B	22		27-61-16	ALL
	H	117	2	W0101	150	22		27-41-11	ALL
	H	117	2	W0101	151	22		27-41-11	ALL
	H	117	2	W0101	152	22		27-41-11	ALL
	H	117	2	W0101	166	22		27-41-11	ALL
	H	117	2	W0101	603	22		27-41-11	ALL
	G	12	2	W0101	208R	22		27-61-14	ALL
	G	12	2	W0101	209R	22		27-61-14	ALL
	G	12	2	W0101	210R	22		27-61-14	ALL
	H	121	2	W0121	003	22		27-09-13	ALL
	H	121	2	W1101	008	22		22-21-11	ALL
	H	121	2	W1101	016	22		27-09-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 8

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		<b>284T0384 (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
	H	121	2	W1101	018	22		27-09-11	ALL
	H	121	2	W1101	019	22		27-09-11	ALL
	H	121	2	W1101	109	22		27-61-14	ALL
	H	121	2	W1101	111	22		27-61-15	ALL
	H	121	2	W1101	113	22		27-61-16	ALL
	H	123	2	W1101	026	22		27-09-14	ALL
	H	123	2	W1101	029	22		27-09-14	ALL
	H	123	2	W1101	030	22		27-09-14	ALL
	H	123	2	W1101	031	22		27-09-14	ALL
	H	123	2	W1101	116	22		27-09-14	ALL
	G	125	2	W1101	022	22		27-09-14	ALL
	G	125	2	W1101	027	22		27-09-14	ALL
	G	125	2	W1101	032	22		27-09-14	ALL
	G	126	2	W1101	050	22		27-11-12	ALL
	G	126	2	W1101	051	22		27-11-12	ALL
	G	126	2	W1101	052	22		27-11-12	ALL
	G	126	2	W1101	053	22		27-11-12	ALL
	G	127	2	W1101	054	22		27-21-12	ALL
	G	127	2	W1101	055	22		27-21-12	ALL
	G	127	2	W1101	056	22		27-21-12	ALL
	G	127	2	W1101	057	22		27-21-12	ALL
	H	128	2	W1101	072	22		27-61-12	ALL
	H	128	2	W1101	073	22		27-61-12	ALL
	H	128	2	W1101	074	22		27-61-12	ALL
	H	128	2	W1101	075	22		27-61-12	ALL
	H	128	2	W1101	076	22		27-61-12	ALL
	H	128	2	W1101	077	22		27-61-12	ALL
	G	13	2	W0101	208B	22		27-61-14	ALL
	G	13	2	W0101	209B	22		27-61-14	ALL
	G	13	2	W0101	210B	22		27-61-14	ALL
	G	142	2	W0121	203R	22		27-61-15	ALL
	G	142	2	W0121	205R	22		27-61-15	ALL
	G	142	2	W0121	206R	22		27-61-15	ALL
	G	143	2	W0121	203B	22		27-61-15	ALL
	G	143	2	W0121	205B	22		27-61-15	ALL
	G	143	2	W0121	206B	22		27-61-15	ALL
	H	144	2	W0121	201R	22		27-61-14	ALL
	H	144	2	W0121	207R	22		27-61-15	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 9

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		<b>284T0384 (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
	H	144	2	W0121	208R	22		27-61-16	ALL
	H	144	2	W0121	209R	22		27-61-16	ALL
	H	144	2	W0121	210R	22		27-61-16	ALL
	H	144	2	W0121	211R	22		27-61-16	ALL
	H	146	2	W0121	133	22		27-61-16	ALL
	H	146	2	W0121	201B	22		27-61-14	ALL
	H	146	2	W0121	207B	22		27-61-15	ALL
	H	146	2	W0121	208B	22		27-61-16	ALL
	H	146	2	W0121	209B	22		27-61-16	ALL
	H	146	2	W0121	210B	22		27-61-16	ALL
	H	146	2	W0121	211B	22		27-61-16	ALL
	H	148	2	W0121	083	22		27-61-11	ALL
	H	148	2	W0121	084	22		27-61-11	ALL
	H	148	2	W0121	085	22		27-61-11	ALL
	H	148	2	W0121	086	22		27-61-11	ALL
	H	148	2	W0121	087	22		27-61-11	ALL
	H	151	2	W0121	011	22		27-09-13	ALL
	H	151	2	W0121	013	22		27-09-13	ALL
	H	151	2	W0121	075	22		27-09-13	ALL
	H	151	2	W0121	077	22		27-09-13	ALL
	H	151	2	W0121	079	22		27-09-13	ALL
	H	151	2	W0121	082	22		27-09-13	ALL
	H	153	2	W0121	010	22		27-09-13	ALL
	H	153	2	W0121	012	22		27-09-13	ALL
	H	153	2	W0121	076	22		27-09-13	ALL
	H	153	2	W0121	078	22		27-09-13	ALL
	H	153	2	W0121	080	22		27-09-13	ALL
	H	153	2	W0121	081	22		27-09-13	ALL
	H	155	2	W0121	009	22		27-09-12	ALL
	H	155	2	W0121	069	22		27-09-12	ALL
	H	155	2	W0121	070	22		27-09-12	ALL
	H	155	2	W0121	071	22		27-09-12	ALL
	H	155	2	W0121	072	22		27-09-12	ALL
	H	155	2	W0121	073	22		27-09-12	ALL
	H	155	2	W0121	074	22		27-09-12	ALL
	G	157	2	W0121	095	22		22-24-11	ALL
	G	157	2	W0121	096	22		22-24-11	ALL
	G	157	2	W0121	097	22		22-24-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 10

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		<b>284T0384 (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
	G	164	2	W0111	150	22		27-41-11	ALL
	G	164	2	W0111	153	22		27-41-11	ALL
	G	164	2	W0111	154	22		27-41-11	ALL
	H	165	2	W0111	219R	22		22-21-11	ALL
	H	165	2	W0111	220R	22		22-21-11	ALL
	H	165	2	W0111	223R	22		27-21-12	ALL
	H	165	2	W0111	224R	22		27-21-12	ALL
	H	165	2	W0111	225R	22		27-21-12	ALL
	H	165	2	W0111	226R	22		27-21-12	ALL
	H	167	2	W0111	118	22		27-21-12	ALL
	H	167	2	W0111	219B	22		22-21-11	ALL
	H	167	2	W0111	220B	22		22-21-11	ALL
	H	167	2	W0111	223B	22		27-21-12	ALL
	H	167	2	W0111	224B	22		27-21-12	ALL
	H	167	2	W0111	225B	22		27-21-12	ALL
	H	167	2	W0111	226B	22		27-21-12	ALL
	H	169	2	W0111	205R	22		27-61-14	ALL
	H	169	2	W0111	206R	22		27-61-14	ALL
	H	169	2	W0111	207R	22		27-61-14	ALL
	H	169	2	W0111	208R	22		27-61-14	ALL
	H	169	2	W0111	209R	22		27-61-15	ALL
	H	169	2	W0111	215R	22		27-61-16	ALL
	H	171	2	W0111	017	22		27-61-14	ALL
	H	171	2	W0111	205B	22		27-61-14	ALL
	H	171	2	W0111	206B	22		27-61-14	ALL
	H	171	2	W0111	207B	22		27-61-14	ALL
	H	171	2	W0111	208B	22		27-61-14	ALL
	H	171	2	W0111	209B	22		27-61-15	ALL
	H	171	2	W0111	215B	22		27-61-16	ALL
	G	173	2	W0111	305R	22		27-61-14	ALL
	G	173	2	W0111	307R	22		27-61-14	ALL
	G	173	2	W0111	309R	22		27-61-15	ALL
	G	173	2	W0111	313R	22		27-61-16	ALL
	G	174	2	W0111	305B	22		27-61-14	ALL
	G	174	2	W0111	307B	22		27-61-14	ALL
	G	174	2	W0111	309B	22		27-61-15	ALL
	G	174	2	W0111	313B	22		27-61-16	ALL
	G	175	2	W0111	305Y	22		27-61-14	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 11

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		284T0384 (continued)					SHELF/E01/01		ALL
TB0101	G	BACM15C1B (continued)					SHELF/E01/01		ALL
TB0101	H	BACM15C2A (continued)					SHELF/E01/01		ALL
	G	175	2	W0111	307Y	22		27-61-14	ALL
	G	175	2	W0111	309Y	22		27-61-15	ALL
	G	175	2	W0111	313Y	22		27-61-16	ALL
	G	176	2	W0111	105	22		27-61-11	ALL
	G	176	2	W0111	106	22		27-61-11	ALL
	G	176	2	W0111	107	22		27-61-11	ALL
	G	176	2	W0111	108	22		27-61-11	ALL
	G	177	2	W0111	148	22		27-41-11	ALL
	G	177	2	W0111	155	22		27-41-11	ALL
	G	177	2	W0111	156	22		27-41-11	ALL
	G	178	2	W0111	149	22		27-41-11	ALL
	G	178	2	W0111	157	22		27-41-11	ALL
	G	178	2	W0111	158	22		27-41-11	ALL
	G	179	2	W0111	082	22		27-09-13	280-299
	G	179	2	W0111	085	22		27-09-13	ALL
	G	179	2	W0111	087	22		27-09-13	ALL
	G	180	2	W0111	083	22		27-09-13	ALL
	G	180	2	W0111	084	22		27-09-13	ALL
	G	180	2	W0111	086	22		27-09-13	ALL
	H	181	2	W0111	075	22		27-09-12	ALL
	H	181	2	W0111	076	22		27-09-12	ALL
	H	181	2	W0111	077	22		27-09-12	ALL
	H	181	2	W0111	078	22		27-09-12	ALL
	H	181	2	W0111	079	22		27-09-12	ALL
	H	181	2	W0111	080	22		27-09-12	ALL
	H	181	2	W0111	081	22		27-09-12	ALL
	G	21	2	W1101	003	22		22-21-11	ALL
	G	21	2	W1101	004	22		22-21-11	ALL
	G	21	2	W1101	005	22		22-21-11	ALL
	G	21	2	W1101	006	22		22-21-11	ALL
	G	23	2	W1101	033	20		27-11-12	ALL
	G	23	2	W1101	034	22		27-11-12	ALL
	G	23	2	W1101	035	22		27-11-12	ALL
	G	24	2	W1101	036	22		27-11-12	ALL
	G	24	2	W1101	037	20		27-11-12	ALL
	G	24	2	W1101	038	20		27-11-12	ALL
	G	25	2	W1101	039	22		27-11-12	ALL
	G	25	2	W1101	040	20		27-11-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 12

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		284T0384 (continued)					SHELF/E01/01		ALL
TB0101	G	BACM15C1B (continued)					SHELF/E01/01		ALL
TB0101	H	BACM15C2A (continued)					SHELF/E01/01		ALL
	G	25	2	W1101	041	20		27-11-12	ALL
	G	26	2	W1101	042	22		27-11-12	ALL
	G	26	2	W1101	043	22		27-11-12	ALL
	G	26	2	W1101	044	22		27-11-12	ALL
	G	27	2	W1101	045	22		27-11-12	ALL
	G	27	2	W1101	046	22		27-11-12	ALL
	G	27	2	W1101	047	22		27-11-12	ALL
	G	28	2	W1101	058	22		27-41-11	ALL
	G	28	2	W1101	059	22		27-41-11	ALL
	G	28	2	W1101	060	22		27-41-11	ALL
	G	28	2	W1101	071	22		27-41-11	ALL
	G	29	2	W1101	061	22		27-41-11	ALL
	G	29	2	W1101	062	22		27-41-11	ALL
	G	29	2	W1101	063	22		27-41-11	ALL
	G	29	2	W1101	064	22		27-41-11	ALL
	G	3	2	W0101	121	22		22-21-11	ALL
	G	3	2	W0101	144	22		22-21-11	ALL
	G	3	2	W0101	145	22		22-21-11	ALL
	G	31	2	W1101	015	22		27-09-14	ALL
	G	31	2	W1101	024	22		27-09-14	ALL
	G	31	2	W1101	117	22		27-09-14	ALL
	G	32	2	W1101	017	22		27-09-14	ALL
	G	32	2	W1101	025	22		27-09-14	ALL
	G	32	2	W1101	118	22		27-09-14	ALL
	G	33	2	W1101	021	22		27-09-14	ALL
	G	33	2	W1101	023	22		27-09-14	ALL
	G	33	2	W1101	119	22		27-09-14	ALL
	G	4	2	W0101	218R	24		22-21-11	ALL
	G	4	2	W0101	220R	24		27-11-12	ALL
	G	4	2	W0101	222R	24		27-11-12	ALL
	G	43	2	W0121	301R	22		27-61-14	ALL
	G	43	2	W0121	303R	22		27-61-15	ALL
	G	43	2	W0121	307R	22		27-61-16	ALL
	G	43	2	W0121	309R	22		27-61-16	ALL
	G	44	2	W0121	301B	22		27-61-14	ALL
	G	44	2	W0121	303B	22		27-61-15	ALL
	G	44	2	W0121	307B	22		27-61-16	ALL
	G	44	2	W0121	309B	22		27-61-16	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 13

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		<b>284T0384 (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
G		45	2	W0121	301Y	22		27-61-14	ALL
G		45	2	W0121	303Y	22		27-61-15	ALL
G		45	2	W0121	307Y	22		27-61-16	ALL
G		45	2	W0121	309Y	22		27-61-16	ALL
G		46	2	W0121	302R	22		27-61-14	ALL
G		46	2	W0121	304R	22		27-61-15	ALL
G		46	2	W0121	308R	22		27-61-16	ALL
G		46	2	W0121	310R	22		27-61-16	ALL
G		47	2	W0121	302B	22		27-61-14	ALL
G		47	2	W0121	304B	22		27-61-15	ALL
G		47	2	W0121	308B	22		27-61-16	ALL
G		47	2	W0121	310B	22		27-61-16	ALL
G		48	2	W0121	302Y	22		27-61-14	ALL
G		48	2	W0121	304Y	22		27-61-15	ALL
G		48	2	W0121	308Y	22		27-61-16	ALL
G		48	2	W0121	310Y	22		27-61-16	ALL
G		49	2	W0121	212R	24		22-21-11	ALL
G		49	2	W0121	214R	24		22-21-11	ALL
G		49	2	W0121	215R	24		22-21-11	ALL
G		5	2	W0101	218B	24		22-21-11	ALL
G		5	2	W0101	220B	24		27-11-12	ALL
G		5	2	W0101	222B	24		27-11-12	ALL
G		50	2	W0121	212B	24		22-21-11	ALL
G		50	2	W0121	214B	24		22-21-11	ALL
G		50	2	W0121	215B	24		22-21-11	ALL
G		51	2	W0121	001	22		22-21-11	ALL
G		51	2	W0121	002	22		22-21-11	ALL
G		51	2	W0121	094	22		22-21-11	ALL
G		52	2	W0121	216R	24		22-22-11	ALL
G		52	2	W0121	217R	24		22-22-11	ALL
G		52	2	W0121	218R	24		22-22-11	ALL
G		53	2	W0121	216B	24		22-22-11	ALL
G		53	2	W0121	217B	24		22-22-11	ALL
G		53	2	W0121	218B	24		22-22-11	ALL
G		54	2	W0121	004	22		22-22-11	ALL
G		54	2	W0121	005	22		22-22-11	ALL
G		54	2	W0121	006	22		22-22-11	ALL
G		6	2	W0101	003	22		27-21-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 14

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		284T0384 (continued)					SHELF/E01/01		ALL
TB0101	G	BACM15C1B (continued)					SHELF/E01/01		ALL
TB0101	H	BACM15C2A (continued)					SHELF/E01/01		ALL
	G	6	2	W0101	005	22		27-21-12	ALL
	G	6	2	W0101	007	22		27-21-12	ALL
	G	62	2	W0111	003	22		27-09-14	ALL
	G	62	2	W0111	089	22		27-09-14	ALL
	G	62	2	W0111	098	22		27-09-14	ALL
	G	64	2	W0111	301R	22		27-21-12	ALL
	G	64	2	W0111	302R	22		27-21-12	ALL
	G	64	2	W0111	303R	22		27-21-12	ALL
	G	65	2	W0111	301B	22		27-21-12	ALL
	G	65	2	W0111	302B	22		27-21-12	ALL
	G	65	2	W0111	303B	22		27-21-12	ALL
	G	66	2	W0111	301Y	22		27-21-12	ALL
	G	66	2	W0111	302Y	22		27-21-12	ALL
	G	66	2	W0111	303Y	22		27-21-12	ALL
	G	67	2	W0111	201R	22		27-21-12	ALL
	G	67	2	W0111	202R	22		27-21-12	ALL
	G	67	2	W0111	203R	22		27-21-12	ALL
	G	68	2	W0111	201B	22		27-21-12	ALL
	G	68	2	W0111	202B	22		27-21-12	ALL
	G	68	2	W0111	203B	22		27-21-12	ALL
	G	69	2	W0111	004	22		27-21-12	ALL
	G	69	2	W0111	005	22		27-21-12	ALL
	G	69	2	W0111	006	22		27-21-12	ALL
	G	70	2	W0111	211R	22		27-61-16	ALL
	G	70	2	W0111	213R	22		27-61-16	ALL
	G	70	2	W0111	214R	22		27-61-16	ALL
	G	71	2	W0111	211B	22		27-61-16	ALL
	G	71	2	W0111	213B	22		27-61-16	ALL
	G	71	2	W0111	214B	22		27-61-16	ALL
	G	72	2	W0111	304R	22		27-61-14	ALL
	G	72	2	W0111	306R	22		27-61-14	ALL
	G	72	2	W0111	308R	22		27-61-15	ALL
	G	72	2	W0111	312R	22		27-61-16	ALL
	G	73	2	W0111	304B	22		27-61-14	ALL
	G	73	2	W0111	306B	22		27-61-14	ALL
	G	73	2	W0111	308B	22		27-61-15	ALL
	G	73	2	W0111	312B	22		27-61-16	ALL
	G	74	2	W0111	304Y	22		27-61-14	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 15

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		<b>284T0384 (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
	G	74	2	W0111	306Y	22		27-61-14	ALL
	G	74	2	W0111	308Y	22		27-61-15	ALL
	G	74	2	W0111	312Y	22		27-61-16	ALL
	G	75	2	W0111	109	22		27-61-12	ALL
	G	75	2	W0111	110	22		27-61-12	ALL
	G	75	2	W0111	111	22		27-61-12	ALL
	G	75	2	W0111	112	22		27-61-12	ALL
	G	76	2	W0111	096	22		27-09-14	ALL
	G	76	2	W0111	097	22		27-09-14	ALL
	G	76	2	W0111	104	22		27-09-14	ALL
	H	77	2	W0111	007	22		27-09-14	ALL
	H	77	2	W0111	101	22		27-09-14	ALL
	H	77	2	W0111	102	22		27-09-14	ALL
	H	77	2	W0111	103	22		27-09-14	ALL
	H	77	2	W0111	181	22		27-09-14	ALL
	G	79	2	W0111	217R	24		22-21-11	ALL
	G	79	2	W0111	221R	24		27-11-12	ALL
	G	79	2	W0111	222R	24		27-11-12	ALL
	G	8	2	W0101	157	22		27-41-11	ALL
	G	8	2	W0101	165	22		27-41-11	ALL
	G	8	2	W0101	167	22		27-41-11	ALL
	G	8	2	W0101	70M	20		29-11-14	ALL
	G	80	2	W0111	217B	24		22-21-11	ALL
	G	80	2	W0111	221B	24		27-11-12	ALL
	G	80	2	W0111	222B	24		27-11-12	ALL
	H	81	2	W0111	015	22		27-61-14	ALL
	H	81	2	W0111	030	22		27-61-15	ALL
	H	81	2	W0111	047	22		27-61-16	ALL
	H	81	2	W0111	071	22		27-09-11	ALL
	H	81	2	W0111	072	22		27-09-11	ALL
	H	81	2	W0111	073	22		27-09-11	ALL
	H	81	2	W0111	131	22		22-21-11	ALL
	G	87	2	W1084	056	24		32-42-12	ALL
	G	87	2	W1084	062	24		32-42-12	ALL
	G	87	2	W1084	069	24		32-42-12	ALL
	G	88	2	W1084	054	24		32-42-12	ALL
	G	88	2	W1084	059	24		32-42-12	ALL
	G	88	2	W1084	077	24		32-42-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 16

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		<b>284T0384 (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
	G	89	2	W1084	003	24		32-42-11	ALL
	G	89	2	W1084	098	24		32-42-11	ALL
	G	89	2	W1084	101	24		32-42-11	ALL
	G	9	2	W0101	302R	22		27-61-14	ALL
	G	9	2	W0101	306R	22		27-61-15	ALL
	G	9	2	W0101	308R	22		27-61-16	ALL
	G	9	2	W0101	312R	22		27-61-15	ALL
	G	93	2	W1084	004	24		32-42-11	ALL
	G	93	2	W1084	097	24		32-42-11	ALL
	G	93	2	W1084	100	24		32-42-11	ALL
	G	94	2	W1084	002	24		32-42-11	ALL
	G	94	2	W1084	079	24		32-42-11	ALL
	G	94	2	W1084	084	24		32-42-11	ALL
	H	95	2	W1084	072	24		32-42-11	ALL
	H	95	2	W1084	075	24		32-42-11	ALL
	H	95	2	W1084	078	24		32-42-11	ALL
	H	95	2	W1084	080	24		32-42-11	ALL
	H	95	2	W1084	081	24		32-42-11	ALL
	G	97	2	W1084	001	24		32-42-11	ALL
	G	97	2	W1084	067	24		32-42-11	ALL
	G	97	2	W1084	099	24		32-42-11	ALL
	G	DED		W0101	018Z			27-41-31	050-099, 155-199, 275-299
	H	DED		W0101	150Z			27-41-11	ALL
	H	DED		W0101	151Z			27-41-11	ALL
	H	DED		W0101	152Z			27-41-11	ALL
	H	DED		W0101	166Z			27-41-11	ALL
	G	DED		W0101	70MZ			29-11-14	050-099, 150-199, 275-278
	Z	DED		W0101	70MZ			29-11-14	280-299
	H	DED		W0111	015Z			27-61-14	ALL
	H	DED		W0111	030Z			27-61-15	ALL
	H	DED		W0111	047Z			27-61-16	ALL
	H	DED		W0111	071Z			27-09-11	ALL
	H	DED		W0111	072Z			27-09-11	ALL
	H	DED		W0111	073Z			27-09-11	ALL
	H	DED		W0111	131Z			22-21-11	ALL
	G	DED		W0121	163Z			27-41-31	050-099, 155-199, 275-299
	H	DED		W1101	008Z			22-21-11	ALL
	H	DED		W1101	016Z			27-09-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 17

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0101		<b>284T0384 (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
TB0101	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/01</b>		<b>ALL</b>
	H	DED		W1101	018Z			27-09-11	ALL
	H	DED		W1101	019Z			27-09-11	ALL
	G	DED		W1101	033Z			27-11-12	ALL
	G	DED		W1101	034Z			27-11-12	ALL
	G	DED		W1101	035Z			27-11-12	ALL
	H	DED		W1101	109Z			27-61-14	ALL
	H	DED		W1101	111Z			27-61-15	ALL
	H	DED		W1101	113Z			27-61-16	ALL
<b>TB0102</b>		<b>BACT442150U</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
<b>TB0102</b>	<b>D</b>	<b>DIODEBLOCK-REF287T4163-</b>					<b>P061-00/ /</b>		<b>ALL</b>
<b>TB0102</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P061-00/ /</b>		<b>050-099, 150-199</b>
<b>TB0102</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P061-00/ /</b>		<b>ALL</b>
<b>TB0102</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P061-00/ /</b>		<b>ALL</b>
<b>TB0102</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P061-00/ /</b>		<b>ALL</b>
<b>TB0102</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Z	19	BJ	W0062	793	22		30-11-11	275-299
	Z	19	BJ	W0066	56A	22		30-11-11	ALL
	Z	19	BJ	W0066	56B	22		30-11-11	ALL
	Z	19	BJ	W0066	881	22		30-11-11	ALL
	Z	19	BJ	W0066	884	22		30-11-11	275-299
	Z	20	BJ	W0066	63A	24		78-36-21	ALL
	Z	20	BJ	W0066	63B	24		78-36-21	ALL
	Z	20	BJ	W0066	63D	24		78-36-21	ALL
	G	41	2	W0066	130	18		25-31-12	050-099, 150-199
	G	41	2	W0066	64Y	18		25-31-11	050-099, 150-199
	G	41	2	W0066	64Y	16		25-31-11	275-299
	G	41	2	W0066	64Z	20		25-31-11	050-099, 150-199, 275-278
	G	41	2	W0066	64Z	18		25-31-11	280-299
	G	41	2	W0066	668	20		25-31-11	050-099, 150-199
	G	41	2	W0066	668	16		25-31-11	275-299
	G	42	2	W0066	656	16		SPARE	280-299
	G	42	2	W0066	65D	16		SPARE	280-299
	G	42	2	W0066	65E	16		SPARE	280-299
	X	A002	BJ	W0062	50P	24		21-44-11	ALL
	X	A002	BJ	W0066	01V	24		21-44-11	ALL
	X	A003	BJ	W0062	687	22		25-31-11	ALL
	X	A003	BJ	W0066	53T	22		25-31-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 18

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0102		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0102	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>050-099, 150-199</b>
TB0102	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	X	A005	BJ	W0062	842	22		30-11-11	275-299
	X	A005	BJ	W0066	56C	22		30-11-11	275-299
	X	A006	BJ	W0062	59H	22		33-25-11	ALL
	X	A006	BJ	W0066	59H	22		33-25-11	ALL
	X	A009	BJ	W0062	407R	22		26-18-12	ALL
	X	A009	BJ	W0066	407R	22		26-18-12	ALL
	F	A011	2	W0062	59B	18		26-13-11	050-099, 150-199
	F	A011	2	W0066	59T	18		26-13-11	050-099, 150-199
	D	A012	2	W0066	58H	20		32-42-12	ALL
	Y	A013	BJ	W0062	643	20		33-11-14	ALL
	Y	A013	BJ	W0066	59L	20		33-11-14	ALL
	Y	A013	BJ	W0066	59M	20		33-11-14	ALL
	Y	A015	BJ	W0062	885	22		29-21-32	ALL
	Y	A015	BJ	W0066	55X	24		29-33-11	ALL
	Y	A015	BJ	W0066	55Y	24		29-33-11	ALL
	Y	A016	BJ	W0062	512	22		21-64-11	ALL
	Y	A016	BJ	W0066	52H	24		21-61-11	ALL
	Y	A016	BJ	W0066	52J	24		21-61-11	ALL
	D	A017	2	W0066	57L	24		32-42-12	ALL
	D	A018	2	W0062	57K	24		32-42-11	ALL
	Y	A026	BJ	W0066	572	22		74-31-21	ALL
	Y	A026	BJ	W0066	62D	22		74-31-21	ALL
	Y	A027	BJ	W0066	57D	22		32-31-11	ALL
	Y	A027	BJ	W0066	57E	22		32-31-11	ALL
	Y	A027	BJ	W0066	57F	22		32-31-11	ALL
	Y	A029	BJ	W0066	006	22		29-32-11	ALL
	Y	A029	BJ	W0066	55T	22		29-32-11	ALL
	Y	A029	BJ	W0066	55U	22		29-32-11	ALL
	Y	A030	BJ	W0062	107	24		21-58-11	ALL
	Y	A030	BJ	W0066	146	24		21-58-11	ALL
	Y	A030	BJ	W0066	51E	24		21-58-11	ALL
	Y	A031	BJ	W0066	56P	22		30-41-12	ALL
	Y	A031	BJ	W0066	56R	22		30-41-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 19

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0102		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0102	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>050-099, 150-199</b>
TB0102	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	A031	BJ	W0066	710	22		30-41-12	ALL
	Y	A033	BJ	W0066	53V	22		27-13-11	ALL
	Y	A033	BJ	W0066	53W	22		27-13-11	ALL
	Y	A033	BJ	W0066	801	22		27-13-11	ALL
	Y	A034	BJ	W0066	511	22		21-61-41	ALL
	Y	A034	BJ	W0066	542	22		21-61-41	ALL
	Y	A034	BJ	W0066	546	22		21-61-41	ALL
	Y	A035	BJ	W0066	508	24		21-61-11	ALL
	Y	A035	BJ	W0066	52M	24		21-61-11	ALL
	Y	A035	BJ	W0066	65F	24		21-61-11	ALL
	Y	A036	BJ	W0066	044	24		21-61-11	ALL
	Y	A036	BJ	W0066	52K	24		21-61-11	ALL
	Y	A036	BJ	W0066	52L	24		21-61-11	ALL
	Y	A037	BJ	W0066	639	22		28-31-11	050-099, 155-199, 276-299
	Y	A037	BJ	W0066	700	20		28-31-11	050-099, 155-199, 276-299
	Y	A037	BJ	W0066	707	20		28-31-11	050-099, 155-199, 276-299
	Y	A038	BJ	W0066	506	22		21-61-21	ALL
	Y	A038	BJ	W0066	52R	22		21-61-21	ALL
	Y	A038	BJ	W0066	52S	22		21-61-21	ALL
	Y	A039	BJ	W0062	75N	22		21-66-21	050-099, 162-199
	Y	A039	BJ	W0066	75J	22		21-66-21	050-099, 162-199
	Y	A040	BJ	W0066	50B	22		21-25-21	ALL
	Y	A040	BJ	W0066	50C	22		21-25-21	ALL
	Y	A040	BJ	W0066	517	22		21-25-21	ALL
	X	B002	BJ	W0062	210R	24		36-21-11	ALL
	X	B002	BJ	W0066	210R	24		36-21-11	ALL
	X	B003	BJ	W0062	210B	24		36-21-11	ALL
	X	B003	BJ	W0066	210B	24		36-21-11	ALL
	X	B005	BJ	W0062	792	22		30-11-11	ALL
	X	B005	BJ	W0066	792	22		30-11-11	ALL
	X	B007	BJ	W0062	525	20		24-51-72	050-099, 162-164, 276
	X	B007	BJ	W0066	502	20		24-51-72	050-099, 162-164, 276
	X	B009	BJ	W0062	414R	22		26-18-22	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 20

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0102		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0102	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>050-099, 150-199</b>
TB0102	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	X	B009	BJ	W0066	414R	22		26-18-22	ALL
	X	B010	BJ	W0062	103	22		78-36-11	ALL
	X	B010	BJ	W0066	118	22		78-36-11	ALL
	X	C001	BJ	W0062	785	24		21-58-11	ALL
	X	C001	BJ	W0066	63W	24		21-58-11	ALL
	X	C002	BJ	W0062	51U	24		21-61-51	ALL
	X	C002	BJ	W0066	533	24		21-61-51	ALL
	X	C005	BJ	W0062	608	24		28-42-31	ALL
	X	C005	BJ	W0066	55M	24		28-42-31	ALL
	X	C007	BJ	W0062	177	24		21-61-81	ALL
	X	C007	BJ	W0066	90A	24		21-61-81	ALL
	X	C008	BJ	W0062	412R	22		26-18-12	ALL
	X	C008	BJ	W0066	412R	22		26-18-12	ALL
	X	C010	BJ	W0062	149	24		21-61-81	ALL
	X	C010	BJ	W0066	185	24		21-61-81	ALL
	D	C012	2	W0066	57Y	24		32-42-12	ALL
	D	C012	2	W0066	58G	24		32-42-12	ALL
	Y	C014	BJ	W0066	57G	24		32-41-11	ALL
	Y	C014	BJ	W0066	57H	24		32-41-11	ALL
	Y	C014	BJ	W0066	57J	24		32-41-11	ALL
	Y	C015	BJ	W0062	51E	24		21-58-11	ALL
	Y	C015	BJ	W0066	137	22		21-58-11	ALL
	Y	C015	BJ	W0066	147	24		21-58-11	ALL
	Y	C015	BJ	W0066	51K	22		21-58-11	ALL
	Y	C016	BJ	W0062	022	24		24-51-71	ALL
	Y	C016	BJ	W0066	001	24		24-51-71	ALL
	Y	C016	BJ	W0066	022	24		24-51-71	ALL
	Y	C016	BJ	W0066	53P	24		24-51-71	ALL
	D	C017	2	W0066	66C	24		32-42-12	ALL
	D	C017	2	W0066	67D	24		32-42-12	ALL
	D	C018	2	W0062	67D	24		32-42-11	ALL
	D	C018	2	W0066	66C	24		32-42-12	ALL
	Y	C027	BJ	W0066	58D	24		32-42-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 21

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0102		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0102	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>050-099, 150-199</b>
TB0102	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	C027	BJ	W0066	58E	24		32-42-12	ALL
	Y	C027	BJ	W0066	58F	24		32-42-12	ALL
	Y	C028	BJ	W0062	113	24		21-58-11	ALL
	Y	C028	BJ	W0066	149	24		21-58-11	ALL
	Y	C029	BJ	W0066	015	22		29-32-11	ALL
	Y	C029	BJ	W0066	55V	22		29-32-11	ALL
	Y	C029	BJ	W0066	55W	22		29-32-11	ALL
	Y	C030	BJ	W0066	018	22		29-11-31	ALL
	Y	C030	BJ	W0066	05S	22		29-11-31	ALL
	Y	C030	BJ	W0066	05T	22		29-11-31	ALL
	Y	C031	BJ	W0066	56S	22		30-41-12	ALL
	Y	C031	BJ	W0066	56T	22		30-41-12	ALL
	Y	C031	BJ	W0066	711	22		30-41-12	ALL
	Y	C032	BJ	W0066	51Y	24		21-58-16	ALL
	Y	C032	BJ	W0066	51Z	24		21-58-16	ALL
	Y	C033	BJ	W0062	130	24		21-43-11	ALL
	Y	C033	BJ	W0062	180	24		21-43-11	ALL
	Y	C033	BJ	W0066	01N	24		21-43-11	ALL
	Y	C036	BJ	W0066	507	22		21-61-31	ALL
	Y	C036	BJ	W0066	52W	22		21-61-31	ALL
	Y	C036	BJ	W0066	52X	22		21-61-31	ALL
	Y	C037	BJ	W0066	139	22		21-58-16	ALL
	Y	C037	BJ	W0066	52A	22		21-58-16	ALL
	Y	C037	BJ	W0066	52B	24		21-58-16	ALL
	Y	C037	BJ	W0066	52C	22		21-58-16	ALL
	Y	C039	BJ	W0066	51A	24		21-53-12	ALL
	Y	C039	BJ	W0066	51B	24		21-53-12	ALL
	Y	C039	BJ	W0066	51C	24		21-53-12	ALL
	Y	CAP	Y	W0066	571	22		SPARE	ALL
	Y	CAP	Y	W0066	62E	22		SPARE	ALL
	X	D001	BJ	W0062	784	24		21-58-11	ALL
	X	D001	BJ	W0066	63V	24		21-58-11	ALL
	X	D002	BJ	W0062	770	22		24-25-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 22

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0102		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0102	<b>D</b>	<b>DIODEBLOCK-REF287T4163- (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>050-099, 150-199</b>
TB0102	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0102	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	X	D002	BJ	W0066	776	22		24-25-11	ALL
	X	D005	BJ	W0062	53S	24		29-11-31	ALL
	X	D005	BJ	W0066	017	24		29-11-31	ALL
	X	D006	BJ	W0062	779	22		24-25-11	ALL
	X	D006	BJ	W0066	787	22		24-25-11	ALL
	X	D007	BJ	W0062	179	24		21-61-81	ALL
	X	D007	BJ	W0066	90B	22		21-61-81	ALL
	X	D008	BJ	W0062	413R	22		26-18-12	ALL
	X	D008	BJ	W0066	413R	22		26-18-12	ALL
	X	DED		W0062	210Z			36-21-11	ALL
	X	DED		W0062	53SZ			29-11-31	ALL
	X	DED		W0062	779Z			24-25-11	ALL
	X	DED		W0062	784Z			21-58-11	ALL
	X	DED		W0062	785Z			21-58-11	ALL
	X	DED		W0062	792Z			30-11-11	ALL
	Z	DED		W0062	793Z			30-11-11	275-299
	Y	DED		W0066	006Z			29-32-11	ALL
	Y	DED		W0066	015Z			29-32-11	ALL
	X	DED		W0066	017Z			29-11-31	ALL
	Y	DED		W0066	55TZ			29-32-11	ALL
	Y	DED		W0066	55UZ			29-32-11	ALL
	Y	DED		W0066	55VZ			29-32-11	ALL
	Y	DED		W0066	55WZ			29-32-11	ALL
	Y	DED		W0066	55XZ			29-33-11	ALL
	Y	DED		W0066	55YZ			29-33-11	ALL
	X	DED		W0066	787Z			24-25-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 23

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0104		<b>BACT442150U</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>F</b>	<b>BACM15C1A</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>G</b>	<b>BACM15C1B</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>X</b>	<b>BACM15C3A</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0104	<b>Y</b>	<b>BACM15C3B</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0104	<b>Z</b>	<b>BACM15C3C</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
	X			W0066	541Z			78-34-21	ALL
	X			W0066	64F	20		78-34-21	ALL
	X			W0066	GRE			78-34-21	ALL
	X	A004	BJ	W0066	659	24		24-22-21	ALL
	X	A004	BJ	W0070	01N	24		24-22-21	ALL
	X	A006	BJ	W0066	64W	20		26-16-21	ALL
	X	A006	BJ	W0070	773	20		26-16-21	ALL
	X	A010	BJ	W0066	195	20		73-21-11	ALL
	X	A010	BJ	W0070	195	20		73-21-11	ALL
	Y	A012	BJ	W0066	62F	22		74-31-21	ALL
	Y	A012	BJ	W0066	62G	22		74-31-21	ALL
	Y	A012	BJ	W0070	136	22		74-31-21	ALL
	Y	A012	BJ	W0070	137	22		74-31-21	ALL
	Y	A013	BJ	W0066	039	22		29-11-21	ALL
	Y	A013	BJ	W0066	55P	22		29-11-21	ALL
	Y	A013	BJ	W0070	03T	22		29-11-21	ALL
	Y	A014	BJ	W0062	129	24		21-43-11	ALL
	Y	A014	BJ	W0062	50N	24		21-43-11	ALL
	Y	A014	BJ	W0070	01C	24		21-43-11	ALL
	Y	A021	BJ	W0066	59R	24		33-14-11	ALL
	Y	A021	BJ	W0066	82C	24		33-14-11	ALL
	Y	A021	BJ	W0066	82E	24		33-14-11	ALL
	Y	A033	BJ	W0066	59Y	22		33-16-12	ALL
	Y	A033	BJ	W0066	59Z	22		33-16-12	ALL
	Y	A033	BJ	W0066	60C	22		33-16-12	ALL
	Y	A035	BJ	W0066	60K	22		33-16-22	ALL
	Y	A035	BJ	W0066	803	22		33-16-26	ALL
	X	A037	BJ	W0066	521	22		28-22-31	ALL
	X	A037	BJ	W0070	587	22		28-22-31	ALL
	X	A038	BJ	W0062	500	22		28-22-31	ALL
	X	A038	BJ	W0066	536	22		28-22-31	ALL
	X	B003	BJ	W0066	01K	24		21-43-11	ALL
	X	B003	BJ	W0070	01D	24		21-43-11	ALL
	X	B004	BJ	W0066	52Z	24		24-22-21	ALL
	X	B004	BJ	W0070	01M	24		24-22-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 24

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0104		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0104	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0104	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
	X	B005	BJ	W0066	170	22		31-31-26	ALL
	X	B005	BJ	W0070	102	22		31-31-26	ALL
	X	B006	BJ	W0066	62Y	24		78-34-21	ALL
	X	B006	BJ	W0070	09V	24		78-34-21	ALL
	X	B007	BJ	W0066	66R	24		35-11-13	ALL
	X	B007	BJ	W0070	06S	24		35-11-13	ALL
	X	B010	BJ	W0066	196	20		73-21-11	ALL
	X	B010	BJ	W0070	196	20		73-21-11	ALL
	X	B037	BJ	W0066	530	22		28-22-31	ALL
	X	B037	BJ	W0070	591	22		28-22-31	ALL
	X	B038	BJ	W0062	538	22		28-22-31	ALL
	X	B038	BJ	W0066	537	20		28-22-31	ALL
	X	C004	BJ	W0066	61G	22		36-11-52	ALL
	X	C004	BJ	W0070	06W	22		36-11-52	ALL
	X	C006	BJ	W0066	62H	22		74-31-21	ALL
	X	C006	BJ	W0070	138	22		74-31-21	ALL
	X	C007	BJ	W0066	045	22		33-51-11	ALL
	X	C007	BJ	W0070	045	22		33-51-11	ALL
	X	C009	BJ	W0062	13A	20		78-34-21	ALL
	X	C009	BJ	W0066	541	20		78-34-21	ALL
	Y	C012	BJ	W0066	62W	24		78-34-21	ALL
	Y	C012	BJ	W0066	62X	24		78-34-21	ALL
	Y	C012	BJ	W0070	09U	24		78-34-21	ALL
	Y	C013	BJ	W0066	038	22		29-11-21	ALL
	Y	C013	BJ	W0066	55R	22		29-11-21	ALL
	Y	C013	BJ	W0070	03U	22		29-11-21	ALL
	Y	C014	BJ	W0070	124	20		78-34-21	ALL
	Y	C014	BJ	W0070	128	20		78-34-21	ALL
	Y	C014	BJ	W0070	129	20		78-34-21	ALL
	X	C026	BJ	W0065	113	22		34-61-15	050-099, 150, 153-199, 275-299
	X	C026	BJ	W0065	113	20		34-61-15	151-152
	X	C026	BJ	W0066	611	22		34-61-15	ALL
	Y	C035	BJ	W0066	60S	22		33-16-22	ALL
	Y	C035	BJ	W0066	60W	22		33-16-22	ALL
	Y	C035	BJ	W0066	804	22		33-16-26	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 25

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0104		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0104	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0104	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
	Y	C036	BJ	W0062	540	22		28-22-31	ALL
	Y	C036	BJ	W0062	544	22		28-22-31	ALL
	Y	C036	BJ	W0070	510	22		28-22-31	ALL
	X	C037	BJ	W0066	528	22		28-22-31	ALL
	X	C037	BJ	W0070	509	22		28-22-31	ALL
	X	C038	BJ	W0062	539	22		28-22-31	ALL
	X	C038	BJ	W0066	538	20		28-22-31	ALL
	X	D003	BJ	W0066	64X	20		26-16-21	ALL
	X	D003	BJ	W0070	778	20		26-16-21	ALL
	X	D004	BJ	W0066	083	24		36-11-52	ALL
	X	D004	BJ	W0070	06X	24		36-11-52	ALL
	X	D006	BJ	W0066	62J	24		74-31-21	ALL
	X	D006	BJ	W0070	139	24		74-31-21	ALL
	X	D008	BJ	W0066	177	22		21-28-11	ALL
	X	D008	BJ	W0070	120	22		21-28-11	ALL
	X	D009	BJ	W0062	13AZ			78-34-21	ALL
	X	D009	BJ	W0066	GRE			78-34-21	ALL
	X	D026	BJ	W0065	116	24		34-61-24	050-099, 155-199, 276-299
	X	D026	BJ	W0066	607	24		34-61-24	050-099, 155-199, 276-299
	X	D027	BJ	W0062	63V	20		78-34-21	ALL
	X	D027	BJ	W0070	63S	20		78-34-21	ALL
	X	D037	BJ	W0066	535	22		28-22-31	ALL
	X	D037	BJ	W0070	604	22		28-22-31	ALL
	X	D038	BJ	W0062	543	22		28-22-31	ALL
	X	D038	BJ	W0070	585	22		28-22-31	ALL
	X	DED		W0062	500Z			28-22-31	ALL
	X	DED		W0062	538Z			28-22-31	ALL
	X	DED		W0062	539Z			28-22-31	ALL
	Y	DED		W0062	540Z			28-22-31	ALL
	X	DED		W0062	543Z			28-22-31	ALL
	Y	DED		W0062	544Z			28-22-31	ALL
	X	DED		W0062	63VZ			78-34-21	ALL
	X	DED		W0066	177Z			21-28-11	050-099
	X	DED		W0066	521Z			28-22-31	ALL
	X	DED		W0066	528Z			28-22-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 26

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0104		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0104	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0104	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0104	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
	X	DED		W0066	530Z			28-22-31	ALL
	X	DED		W0066	535Z			28-22-31	ALL
	X	DED		W0066	536Z			28-22-31	ALL
	X	DED		W0066	537Z			28-22-31	ALL
	X	DED		W0066	538Z			28-22-31	ALL
	Y	DED		W0066	59YZ			33-16-12	ALL
	Y	DED		W0066	59ZZ			33-16-12	ALL
	Y	DED		W0066	60CZ			33-16-12	ALL
	Y	DED		W0066	62FZ			74-31-21	ALL
	Y	DED		W0066	62GZ			74-31-21	ALL
	X	DED		W0066	62HZ			74-31-21	ALL
	Y	DED		W0070	03TZ			29-11-21	ALL
	Y	DED		W0070	03UZ			29-11-21	ALL
	Y	DED		W0070	09UZ			78-34-21	ALL
	X	DED		W0070	09VZ			78-34-21	ALL
	X	DED		W0070	102Z			31-31-26	ALL
	X	DED		W0070	120Z			21-28-11	050-099
	Y	DED		W0070	136Z			74-31-21	ALL
	Y	DED		W0070	137Z			74-31-21	ALL
	X	DED		W0070	138Z			74-31-21	ALL
	X	DED		W0070	139Z			74-31-21	ALL
	Y	DED		W0070	510Z			28-22-31	ALL
TB0105		<b>284T0384-8</b>					<b>SHELF/E01/03</b>		<b>ALL</b>
TB0105	<b>D</b>	<b>BACM15C1A</b>					<b>SHELF/E01/03</b>		<b>050-099</b>
TB0105	<b>D</b>	<b>DIODEBLOCK-REF284T0113-</b>					<b>SHELF/E01/03</b>		<b>150-199, 275-299</b>
TB0105	<b>F</b>	<b>BACM15C1A</b>					<b>SHELF/E01/03</b>		<b>ALL</b>
TB0105	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E01/03</b>		<b>ALL</b>
TB0105	<b>H</b>	<b>BACM15C2A</b>					<b>SHELF/E01/03</b>		<b>ALL</b>
TB0105	<b>X</b>	<b>BACM15C3A</b>					<b>SHELF/E01/03</b>		<b>050-099, 275-299</b>
TB0105	<b>Y</b>	<b>BACM15C3B</b>					<b>SHELF/E01/03</b>		<b>ALL</b>
TB0105	<b>Z</b>	<b>BACM15C3B</b>					<b>SHELF/E01/03</b>		<b>ALL</b>
	G	10	2	W0105	170	24		27-48-11	ALL
	G	10	2	W0105	171	24		27-48-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 27

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	G	10	2	W0105	174	24		27-48-11	ALL
	G	101	2	W0105	371R	24		34-12-11	ALL
	G	101	2	W0105	375R	24		34-12-11	ALL
	G	101	2	W0105	376R	24		34-12-11	ALL
	G	102	2	W0105	371B	24		34-12-11	ALL
	G	102	2	W0105	375B	24		34-12-11	ALL
	G	102	2	W0105	376B	24		34-12-11	ALL
	G	103	2	W0105	371Y	24		34-12-11	ALL
	G	103	2	W0105	375Y	24		34-12-11	ALL
	G	103	2	W0105	376Y	24		34-12-11	ALL
	H	107	2	W0105	150	24		34-12-61	ALL
	H	107	2	W0105	191	24		34-12-12	ALL
	H	107	2	W0105	820	24		34-12-12	ALL
	H	107	2	W0105	823	24		31-51-21	ALL
	G	109	2	W0105	069	24		22-15-12	ALL
	G	109	2	W0105	079	24		22-15-12	ALL
	G	109	2	W0105	160	24		22-15-12	ALL
	H	11	2	W0105	501R	24		27-11-12	ALL
	H	11	2	W0105	510R	24		34-12-12	ALL
	H	11	2	W0105	525R	24		34-12-61	ALL
	H	11	2	W0125	555R	24		34-16-11	ALL
	G	110	2	W0105	784	24		34-45-13	ALL
	G	110	2	W0115	036	24		34-45-13	050-099, 150-199, 277-299
	G	111	2	W0105	813	24		34-12-12	ALL
	G	111	2	W0105	828	24		34-12-12	ALL
	G	111	2	W0105	830	24		34-12-12	ALL
	H	112	2	W0105	131	22		34-45-12	ALL
	H	112	2	W0105	132	22		34-45-12	ALL
	H	112	2	W0105	133	22		34-45-12	ALL
	H	112	2	W0105	901	22		34-45-12	ALL
	H	112	2	W0105	902	22		34-45-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 28

Jun 28/2006



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	112	2	W0105	905	22		34-45-12	ALL
	H	112	2	W0105	906	22		34-45-12	ALL
	H	112	2	W0105	907	22		34-45-12	ALL
	H	112	2	W0115	049	24		22-14-21	050-099
	G	114	2	W0105	231R	24		22-15-11	ALL
	G	114	2	W0125	231R	24		22-15-11	ALL
	G	115	2	W0105	231B	24		22-15-11	ALL
	G	115	2	W0125	231B	24		22-15-11	ALL
	G	116	2	W0105	058	24		22-14-11	ALL
	G	116	2	W0115	058	24		22-14-11	ALL
	G	116	2	W0115	063	24		22-14-11	ALL
	G	118	2	W0105	062	24		22-14-11	ALL
	G	118	2	W0115	050	24		22-14-11	ALL
	G	118	2	W0115	053	24		22-14-11	ALL
	G	121	2	W0105	593	22		34-45-12	ALL
	G	121	2	W0105	594	22		34-45-12	ALL
	G	121	2	W0105	595	22		34-45-12	ALL
	H	125	2	W0105	001	22		22-11-12	ALL
	H	125	2	W0105	002	20		22-11-12	ALL
	H	125	2	W0105	005	22		22-11-12	ALL
	H	125	2	W0105	008	22		22-11-12	ALL
	H	125	2	W0105	023	22		22-11-12	ALL
	H	13	2	W0105	501B	24		27-11-12	ALL
	H	13	2	W0105	510B	24		34-12-12	ALL
	H	13	2	W0105	525B	24		34-12-61	ALL
	H	13	2	W0125	555B	24		34-16-11	ALL
	H	130	2	W0105	822	22		34-12-12	ALL
	H	130	2	W0105	831	22		34-12-12	ALL
	H	130	2	W0105	850	22		34-12-12	ALL
	H	130	2	W0105	863	22		34-12-12	ALL
	H	130	2	W0105	864	22		34-12-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 29

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	130	2	W0105	865	22		34-12-12	050-099
	G	132	2	W0105	233B	24		22-15-11	ALL
	G	132	2	W0115	233B	24		22-15-11	ALL
	G	133	2	W0105	233R	24		22-15-11	ALL
	G	133	2	W0115	233R	24		22-15-11	ALL
	G	138	2	W0105	188	24		34-12-22	ALL
	G	138	2	W0115	188	24		34-12-22	ALL
	G	139	2	W0105	802	20		34-12-11	ALL
	G	139	2	W0125	003	22		34-12-11	ALL
	G	139	2	W0125	105	22		34-12-11	ALL
	H	143	2	W0105	502R	20		34-12-11	ALL
	H	143	2	W0125	106	22		34-12-11	ALL
	H	143	2	W0125	205R	22		34-12-11	ALL
	H	143	2	W0125	206R	22		34-12-11	ALL
	H	146	2	W0105	299R	24		34-22-19	ALL
	H	146	2	W0105	513R	24		34-12-12	ALL
	H	146	2	W0105	514R	24		34-21-11	ALL
	H	146	2	W0105	529R	24		34-22-39	ALL
	H	146	2	W0105	895R	24		34-13-11	ALL
	H	146	2	W0115	215R	24		34-12-62	ALL
	H	148	2	W0105	299B	24		34-22-19	ALL
	H	148	2	W0105	513B	24		34-12-12	ALL
	H	148	2	W0105	514B	24		34-21-11	ALL
	H	148	2	W0105	529B	24		34-22-39	ALL
	H	148	2	W0105	895B	24		34-13-11	ALL
	H	148	2	W0115	215B	24		34-12-62	ALL
	H	15	2	W0105	217R	24		22-12-31	ALL
	H	15	2	W0105	218R	24		22-12-11	ALL
	H	15	2	W0105	273R	24		34-12-61	ALL
	H	15	2	W0105	525R	24		34-12-61	ALL
	H	15	2	W0105	662R	24		22-32-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 30

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	150	2	W0105	724	22		22-32-14	050-099, 275-299
	H	150	2	W0105	725	22		22-32-14	050-099, 275-299
	H	150	2	W0105	743	22		22-32-14	050-099, 275-299
	H	150	2	W0105	744	22		22-32-14	050-099, 275-299
	H	150	#	W0105	776	22		22-32-14	050-099, 275-299
	H	150	2	W0105	777	22		22-32-14	050-099, 275-299
	H	150	2	W0105	781	22		22-32-14	050-099
	H	150	#	W0105	781	22		22-32-14	275-299
	H	150	2	W0105	789	20		22-32-14	050-099, 275-299
	H	152	#	W0105	712	22		22-32-14	050-099
	H	152	2	W0105	712	22		22-32-14	275-299
	H	152	2	W0105	720	22		22-32-14	050-099, 275-299
	H	152	2	W0105	721	22		22-32-14	050-099, 275-299
	H	152	2	W0105	722	22		22-32-14	050-099, 275-299
	H	152	#	W0105	723	22		22-32-14	275-299
	H	152	#	W0105	778	22		22-32-14	050-099, 275-299
	H	152	2	W0105	790	20		22-32-14	050-099, 275-299
	H	154	2	W0105	768	22		22-32-14	050-099, 275-299
	H	154	#	W0105	772	22		22-32-14	050-099, 275-299
	H	154	2	W0105	773	22		22-32-14	050-099, 275-299
	H	154	2	W0105	774	22		22-32-14	050-099, 275-299
	H	154	2	W0105	775	22		22-32-14	050-099, 275-299
	H	154	2	W0105	788	20		22-32-14	050-099, 275-299
	G	156	2	W0105	240R	24		34-12-61	ALL
	G	156	2	W0105	277R	24		34-12-61	ALL
	G	156	2	W0115	219R	24		31-31-12	ALL
	G	157	2	W0105	240B	24		34-12-61	ALL
	G	157	2	W0105	277B	24		34-12-61	ALL
	G	157	2	W0115	219B	24		31-31-12	ALL
	G	158	2	W0105	589	22		34-45-14	050-099, 150-152, 155-199, 275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 31

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	G	158	2	W0105	903	22		34-45-14	050-099, 150-152, 155-199, 275-299
	G	158	2	W0115	034	22		34-45-14	155-199, 277-299
	G	161	2	W0105	289R	24		31-51-21	ALL
	G	161	2	W0105	290R	24		34-33-11	ALL
	G	161	2	W0105	292R	24		34-33-11	ALL
	G	161	2	W0105	568R	24		34-45-14	ALL
	G	162	2	W0105	289B	24		31-51-21	ALL
	G	162	2	W0105	290B	24		34-33-11	ALL
	G	162	2	W0105	292B	24		34-33-11	ALL
	G	162	2	W0105	568B	24		34-45-14	ALL
	H	163	2	W0105	700	24		22-32-14	275-299
	H	163	2	W0105	727	22		22-32-14	275-299
	H	163	2	W0105	728	22		22-32-14	275-299
	H	163	2	W0105	729	22		22-32-14	275-299
	H	163	2	W0105	742	22		22-32-14	275-299
	Z	165	BJ	W0105	252R	24		34-31-11	ALL
	Z	165	BJ	W0105	253R	24		34-22-19	ALL
	Z	165	BJ	W0105	258R	24		34-61-12	ALL
	Z	165	BJ	W0105	259R	24		34-46-12	ALL
	Z	165	BJ	W0105	574R	24		31-31-20	ALL
	Z	166	BJ	W0105	252B	24		34-31-11	ALL
	Z	166	BJ	W0105	253B	24		34-22-19	ALL
	Z	166	BJ	W0105	258B	24		34-61-12	ALL
	Z	166	BJ	W0105	259B	24		34-46-12	ALL
	Z	166	BJ	W0105	574B	24		31-31-20	ALL
	H	168	2	W0105	534R	24		22-32-12	ALL
	H	168	2	W0105	536R	24		73-21-14	ALL
	H	168	2	W0105	541R	24		22-32-12	ALL
	H	168	2	W0115	206R	24		73-21-14	ALL
	H	168	2	W0115	552R	24		73-21-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 32

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	17	2	W0105	217B	24		22-12-31	ALL
	H	17	2	W0105	218B	24		22-12-11	ALL
	H	17	2	W0105	273B	24		34-12-61	ALL
	H	17	2	W0105	525B	24		34-12-61	ALL
	H	17	2	W0105	662B	24		22-32-11	ALL
	H	170	2	W0105	534B	24		22-32-12	ALL
	H	170	2	W0105	536B	24		73-21-14	ALL
	H	170	2	W0105	541B	24		22-32-12	ALL
	H	170	2	W0115	206B	24		73-21-14	ALL
	H	170	2	W0115	552B	24		73-21-14	ALL
	G	178	2	W0105	552R	24		31-31-14	050-099
	G	178	2	W0105	552R	22		31-31-14	150-199, 275-299
	G	178	2	W0105	689R	24		22-32-12	ALL
	G	178	2	W0105	691R	24		22-32-12	ALL
	G	178	2	W0105	699R	24		22-32-12	ALL
	G	179	2	W0105	552B	24		31-31-14	050-099
	G	179	2	W0105	552B	22		31-31-14	150-199, 275-299
	G	179	2	W0105	689B	24		22-32-12	ALL
	G	179	2	W0105	691B	24		22-32-12	ALL
	G	179	2	W0105	699B	24		22-32-12	ALL
	G	185	2	W0105	762	22		22-34-11	ALL
	G	185	2	W0105	763	22		22-34-11	ALL
	G	185	2	W0105	764	22		22-34-11	ALL
	G	186	2	W0105	584	22		34-45-13	050-099, 150-166, 275-276
	G	186	2	W0105	586	22		34-45-13	050-099, 150-166, 275-276
	G	186	2	W0105	779	22		34-45-13	050-099, 150-166, 275-276
	G	187	2	W0105	709	20		22-31-12	ALL
	G	187	2	W0125	709	20		22-31-12	ALL
	H	188	2	W0105	055	24		22-14-11	ALL
	H	188	2	W0125	057	24		22-14-11	ALL
	H	188	2	W0125	059	24		22-14-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 33

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	188	2	W0125	060	24		22-14-31	ALL
	H	188	2	W0125	089	24		22-14-21	ALL
	H	19	2	W0105	053	24		22-14-11	ALL
	H	19	2	W0105	054	24		22-14-11	ALL
	H	19	2	W0105	064	24		22-14-31	ALL
	H	19	2	W0105	073	24		22-14-31	ALL
	H	19	2	W0115	049	24		22-14-21	150-199, 275-299
	G	192	2	W0105	656R	24		22-32-11	ALL
	G	192	2	W0115	205R	24		34-22-39	ALL
	G	192	2	W0115	527R	24		34-22-19	ALL
	G	192	2	W0115	656R	24		22-32-11	ALL
	G	193	2	W0105	656B	24		22-32-11	ALL
	G	193	2	W0115	205B	24		34-22-39	ALL
	G	193	2	W0115	527B	24		34-22-19	ALL
	G	193	2	W0115	656B	24		22-32-11	ALL
	G	194	2	W0105	539B	24		77-35-11	ALL
	G	194	2	W0105	540B	24		77-35-11	ALL
	G	194	2	W0105	576B	24		31-35-12	ALL
	G	194	2	W0105	677B	24		22-33-11	ALL
	G	195	2	W0105	539R	24		77-35-11	ALL
	G	195	2	W0105	540R	24		77-35-11	ALL
	G	195	2	W0105	576R	24		31-35-12	ALL
	G	195	2	W0105	677R	24		22-33-11	ALL
	G	196	2	W0105	537B	24		77-35-11	ALL
	G	196	2	W0105	538B	24		77-35-11	ALL
	G	196	2	W0105	575B	24		31-35-12	ALL
	G	196	2	W0105	679B	24		22-33-11	ALL
	G	197	2	W0105	537R	24		77-35-11	ALL
	G	197	2	W0105	538R	24		77-35-11	ALL
	G	197	2	W0105	575R	24		31-35-12	ALL
	G	197	2	W0105	679R	24		22-33-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 34

Jun 28/2006



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	G	2	2	W0105	128	24		34-12-61	ALL
	G	2	2	W0105	817	24		34-12-12	ALL
	G	2	2	W0115	039	24		34-12-62	ALL
	H	21	2	W0105	017	22		22-11-12	ALL
	H	21	2	W0105	018	22		22-11-12	ALL
	H	21	2	W0105	019	22		22-11-12	ALL
	H	21	2	W0115	051	22		22-11-22	ALL
	H	21	2	W0125	025	22		22-11-32	ALL
	G	23	2	W0105	208R	24		22-12-11	ALL
	G	23	2	W0105	214R	24		22-12-11	ALL
	G	23	2	W0105	236R	24		22-22-11	ALL
	G	24	2	W0105	208B	24		22-12-11	ALL
	G	24	2	W0105	214B	24		22-12-11	ALL
	G	24	2	W0105	236B	24		22-22-11	ALL
	G	25	2	W0105	003	22		22-11-12	ALL
	G	25	2	W0105	011	22		22-11-12	ALL
	G	25	2	W0105	052	22		22-14-11	ALL
	G	27	2	W0105	213R	24		22-12-11	ALL
	G	27	2	W0105	220R	24		22-12-31	ALL
	G	27	2	W0105	242R	24		34-61-15	ALL
	G	27	2	W0105	533R	24		27-32-11	ALL
	G	28	2	W0105	213B	24		22-12-11	ALL
	G	28	2	W0105	220B	24		22-12-31	ALL
	G	28	2	W0105	242B	24		34-61-15	ALL
	G	28	2	W0105	533B	24		27-32-11	ALL
	G	29	2	W0105	010	22		22-11-12	ALL
	G	29	2	W0105	012	22		22-11-12	ALL
	G	29	2	W0105	013	22		22-11-12	ALL
	G	30	2	W0105	060	22		22-14-11	ALL
	G	30	2	W0105	066	22		22-14-21	ALL
	G	30	2	W0105	068	22		22-14-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 35

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	G	30	2	W0105	070	22		22-14-31	ALL
	G	31	2	W0105	092	24		22-13-11	ALL
	G	31	2	W0105	093	24		22-13-11	ALL
	G	31	2	W0105	094	22		34-22-16	ALL
	G	31	2	W0105	106	22		34-61-14	ALL
	H	32	2	W0105	204B	20		22-11-11	ALL
	H	32	2	W0105	205B	22		22-11-11	ALL
	H	32	2	W0105	206B	22		22-11-11	ALL
	H	32	2	W0105	207B	22		22-11-11	ALL
	H	34	2	W0105	204R	20		22-11-11	ALL
	H	34	2	W0105	205R	22		22-11-11	ALL
	H	34	2	W0105	206R	22		22-11-11	ALL
	H	34	2	W0105	207R	22		22-11-11	ALL
	H	37	2	W0105	503R	20		34-12-11	ALL
	H	37	2	W0105	504R	20		34-12-11	ALL
	H	37	2	W0105	507R	22		34-12-11	ALL
	H	37	2	W0125	107	22		34-12-11	ALL
	G	39	2	W0105	038	22		22-12-11	ALL
	G	39	2	W0105	039	22		22-12-11	ALL
	G	39	2	W0105	758	24		22-32-15	ALL
	H	4	2	W0105	511R	24		34-12-12	ALL
	H	4	2	W0105	512R	24		34-12-12	ALL
	H	4	2	W0105	515R	24		34-46-12	ALL
	H	4	2	W0105	517R	24		21-31-11	ALL
	H	4	2	W0105	520R	24		34-12-61	ALL
	H	4	2	W0105	523R	24		27-51-51	ALL
	H	4	2	W0105	530R	24		34-13-21	ALL
	H	4	2	W0105	695R	24		31-41-31	ALL
	G	40	2	W0105	215B	24		22-12-11	ALL
	G	40	2	W0105	216B	24		22-12-11	ALL
	G	40	2	W0105	219B	24		22-12-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 36

Jun 28/2006



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	G	41	2	W0105	215R	24		22-12-11	ALL
	G	41	2	W0105	216R	24		22-12-11	ALL
	G	41	2	W0105	219R	24		22-12-11	ALL
	Z	44	%	W0105	890	24		31-31-19	150-199, 275-299
	G	47	2	W0105	141	22		34-45-14	050-099, 150-156, 162-166, 275-276
	G	47	2	W0105	785	22		34-45-14	050-099, 150-156, 162-166, 275-276
	G	47	2	W0105	904	22		34-45-14	050-099, 150-156, 162-166, 275-276
	G	48	2	W0105	045	24		22-13-11	ALL
	G	48	2	W0105	107	22		34-31-11	ALL
	G	48	2	W0105	109	24		22-13-11	ALL
	H	49	2	W0105	295R	24		34-61-12	ALL
	H	49	2	W0105	520R	24		34-12-61	ALL
	H	49	2	W0105	577R	24		31-35-12	ALL
	H	49	2	W0105	894R	24		34-21-21	ALL
	H	49	2	W0105	896R	24		27-11-22	ALL
	H	51	2	W0105	295B	24		34-61-12	ALL
	H	51	2	W0105	520B	24		34-12-61	ALL
	H	51	2	W0105	577B	24		31-35-12	ALL
	H	51	2	W0105	894B	24		34-21-21	ALL
	H	51	2	W0105	896B	24		27-11-22	ALL
	G	54	2	W0105	141	22		34-45-14	157, 167-199, 277-299
	G	54	2	W0105	785	22		34-45-14	157, 167-199, 277-299
	G	54	2	W0105	904	22		34-45-14	157, 277-299
	H	55	2	W0105	664R	24		22-32-12	ALL
	H	55	2	W0105	684R	24		34-22-39	ALL
	H	55	2	W0105	686R	24		22-14-11	ALL
	H	55	2	W0105	687R	24		34-22-19	ALL
	H	55	2	W0105	690R	24		34-61-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 37

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	57	2	W0105	664B	24		22-32-12	ALL
	H	57	2	W0105	684B	24		34-22-39	ALL
	H	57	2	W0105	686B	24		22-14-11	ALL
	H	57	2	W0105	687B	24		34-22-19	ALL
	H	57	2	W0105	690B	24		34-61-12	ALL
	G	59	2	W0105	075	24		22-15-12	ALL
	G	59	2	W0105	076	24		22-15-12	ALL
	G	59	2	W0105	077	24		22-15-12	ALL
	H	6	2	W0105	511B	24		34-12-12	ALL
	H	6	2	W0105	512B	24		34-12-12	ALL
	H	6	2	W0105	515B	24		34-46-12	ALL
	H	6	2	W0105	517B	24		21-31-11	ALL
	H	6	2	W0105	520B	24		34-12-61	ALL
	H	6	2	W0105	523B	24		27-51-51	ALL
	H	6	2	W0105	530B	24		34-13-21	ALL
	H	6	2	W0105	695B	24		31-41-31	ALL
	G	60	2	W0105	250R	24		34-22-38	ALL
	G	60	2	W0105	268R	24		34-22-18	ALL
	G	60	2	W0105	269R	24		34-22-18	ALL
	G	61	2	W0105	250B	24		34-22-38	ALL
	G	61	2	W0105	268B	24		34-22-18	ALL
	G	61	2	W0105	269B	24		34-22-18	ALL
	G	62	2	W0105	255R	24		34-31-11	ALL
	G	62	2	W0105	256R	24		34-31-11	ALL
	G	62	2	W0105	257R	24		34-31-11	ALL
	G	63	2	W0105	255B	24		34-31-11	ALL
	G	63	2	W0105	256B	24		34-31-11	ALL
	G	63	2	W0105	257B	24		34-31-11	ALL
	G	64	2	W0105	081	22		22-22-11	ALL
	G	64	2	W0105	082	24		22-12-11	ALL
	G	64	2	W0105	083	24		22-12-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 38

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	67	2	W0105	221R	24		22-13-11	ALL
	H	67	2	W0105	222R	24		22-13-11	ALL
	H	67	2	W0105	223R	24		22-13-11	ALL
	H	67	2	W0105	241R	24		34-61-14	ALL
	H	67	2	W0105	655R	24		22-32-11	ALL
	H	67	2	W0105	986R	24		34-53-11	275-299
	H	69	2	W0105	221B	24		22-13-11	ALL
	H	69	2	W0105	222B	24		22-13-11	ALL
	H	69	2	W0105	223B	24		22-13-11	ALL
	H	69	2	W0105	241B	24		34-61-14	ALL
	H	69	2	W0105	655B	24		22-32-11	ALL
	H	69	2	W0105	986B	24		34-53-11	275-299
	G	71	2	W0105	110	24		34-31-11	ALL
	G	71	2	W0105	111	24		34-57-11	ALL
	G	71	2	W0105	112	24		34-55-11	ALL
	G	71	2	W0105	113	24		34-55-11	ALL
	G	73	2	W0105	546R	24		34-45-14	050-099, 150-156, 162-166, 275-276
	G	73	2	W0105	583R	24		34-45-14	050-099, 150-156, 162-166, 275-276
	G	73	2	W0105	585R	24		34-45-14	050-099, 150-156, 162-166, 275-276
	G	73	2	W0105	588R	24		34-45-14	050-099, 150-156, 162-166, 275-276
	G	74	2	W0105	546B	24		34-45-14	050-099, 150-156, 162-166, 275-276
	G	74	2	W0105	583B	24		34-45-14	050-099, 150-156, 162-166, 275-276
	G	74	2	W0105	585B	24		34-45-14	050-099, 150-156, 162-166, 275-276

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 39

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	G	74	2	W0105	588B	24		34-45-14	050-099, 150-156, 162-166, 275-276
	H	78	2	W0105	700	24		22-32-14	050-099
	G	78	2	W0105	700	24		22-32-14	150-199
	G	78	2	W0105	726	22		22-32-14	150-199
	H	78	2	W0105	727	22		22-32-14	050-099
	G	78	2	W0105	727	22		22-32-14	150-199
	H	78	2	W0105	728	22		22-32-14	050-099
	H	78	2	W0105	729	22		22-32-14	050-099
	G	78	2	W0105	729	22		22-32-14	150-199
	H	78	2	W0105	742	22		22-32-14	050-099
	G	8	2	W0105	123	24		27-48-11	157, 167-199, 277-299
	G	8	2	W0105	173	24		27-48-11	ALL
	G	8	2	W0105	176	24		27-48-11	ALL
	G	8	2	W0105	294R	24		31-31-13	ALL
	H	81	2	W0105	700	24		22-32-14	ALL
	H	81	2	W0105	714	24		22-32-13	ALL
	H	81	2	W0105	717	24		22-32-13	ALL
	H	81	2	W0105	726	22		22-32-14	050-099, 275-299
	H	81	2	W0105	728	22		22-32-14	150-199
	H	81	2	W0105	732	24		22-32-13	ALL
	H	81	2	W0105	742	22		22-32-14	150-199
	H	81	2	W0105	748	24		22-32-15	ALL
	H	81	2	W0105	837	22		22-32-14	ALL
	G	83	2	W0105	238R	24		22-41-12	ALL
	G	83	2	W0105	239R	24		22-41-12	ALL
	G	83	2	W0105	692R	24		22-41-12	ALL
	G	84	2	W0105	238B	24		22-41-12	ALL
	G	84	2	W0105	239B	24		22-41-12	ALL
	G	84	2	W0105	692B	24		22-41-12	ALL
	H	85	2	W0105	659R	24		22-32-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 40

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	85	2	W0105	660R	24		22-32-11	ALL
	H	85	2	W0105	685R	24		34-43-11	ALL
	H	87	2	W0105	659B	24		22-32-11	ALL
	H	87	2	W0105	660B	24		22-32-11	ALL
	H	87	2	W0105	685B	24		34-43-11	ALL
	G	89	2	W0105	701	20		22-31-11	ALL
	G	89	2	W0105	702	20		22-31-11	ALL
	G	89	2	W0105	706	24		22-31-11	ALL
	G	9	2	W0105	122	24		27-48-11	157, 167-199, 277-299
	G	9	2	W0105	172	24		27-48-11	ALL
	G	9	2	W0105	175	24		27-48-11	ALL
	G	9	2	W0105	294B	24		31-31-13	ALL
	G	93	2	W0105	765	24		22-34-11	ALL
	G	93	2	W0105	766	24		22-34-11	ALL
	G	93	2	W0105	854	24		22-34-11	ALL
	G	96	2	W0105	535	24		22-32-13	ALL
	G	96	2	W0105	759	24		22-32-15	ALL
	G	96	2	W0105	760	24		22-32-15	ALL
	D	A001	2	W0105	126	22		34-12-61	ALL
	D	A001	2	W0105	127	20		34-12-61	ALL
	F	A003	2	W0105	235R	24		27-32-11	ALL
	F	A003	2	W0125	202R	24		27-32-11	ALL
	F	A036	2	W0105	518R	24		34-12-61	ALL
	F	A036	2	W0125	203R	24		34-12-61	ALL
	F	A053	2	W0105	653R	22		22-31-12	ALL
	F	A053	2	W0105	654R	22		22-31-12	ALL
	F	A054	2	W0105	590R	24		34-45-14	050-099, 150-156, 162-166, 275-276
	F	A054	2	W0115	211R	24		34-45-14	050-099, 150-156, 162-166
	Y	A073	BJ	W0105	546R	24		34-45-14	157, 167-199, 277-299
	Y	A073	BJ	W0105	583R	24		34-45-14	157, 167-199, 277-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 41

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	Y	A073	BJ	W0105	585R	24		34-45-14	157, 167-199, 277-299
	Y	A073	BJ	W0105	588R	24		34-45-14	157, 167-199, 277-299
	Y	A074	BJ	W0105	590R	24		34-45-14	157, 167-199, 277-299
	Y	A074	BJ	W0105	599R	24		34-45-14	157, 167-199, 277-299
	Y	A074	BJ	W0115	211R	24		34-45-14	157, 167-199, 277-299
	F	A075	2	W0105	246R	24		22-33-11	ALL
	F	A075	2	W0115	208R	24		22-33-11	ALL
	F	A076	2	W0105	531R	24		22-33-11	ALL
	F	A076	2	W0115	207R	24		22-33-11	ALL
	F	A077	2	W0105	605	24		77-35-11	ALL
	F	A077	2	W0115	602	24		77-35-11	ALL
	F	A079	2	W0105	648R	24		22-32-12	150-199, 275-299
	F	A080	2	W0105	648R	24		22-32-12	050-099
	F	A094	2	W0105	153	24		22-32-13	ALL
	F	A095	2	W0105	155	24		22-32-13	ALL
	F	A105	2	W0105	377R	24		34-12-11	ALL
	F	A105	2	W0115	301R	24		34-12-11	ALL
	F	A106	2	W0105	377Y	24		34-12-11	ALL
	F	A106	2	W0115	301Y	24		34-12-11	ALL
	F	A117	2	W0105	063	24		22-14-11	ALL
	F	A117	2	W0125	062	24		22-14-11	ALL
	F	A119	2	W0105	078	24		22-15-12	ALL
	F	A119	2	W0115	078	24		22-15-12	ALL
	F	A122	2	W0105	009	20		22-11-12	ALL
	F	A122	2	W0125	009	22		22-11-12	ALL
	F	A124	2	W0105	582R	24		77-12-11	150-157, 275-276
	F	A124	2	W0115	209R	24		77-12-11	150-157, 275-276
	F	A129	2	W0105	209R	24		31-31-12	ALL
	F	A129	2	W0115	201R	24		31-31-12	ALL
	F	A135	2	W0105	074	24		22-15-12	ALL
	F	A135	2	W0125	074	24		22-15-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 42

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	Y	A141	%	W0105	573R	24		31-31-20	150-199, 275-299
	F	A158	2	W0105	589	22		34-45-14	153-154
	F	A158	2	W0115	034	22		34-45-14	050-099, 150-154
	F	A173	2	W0105	312R	24		22-32-12	ALL
	F	A174	2	W0105	312Y	24		22-32-12	ALL
	F	A176	2	W0105	592R	24		34-45-14	050-099, 150-156, 162-166, 275-276
	F	A176	2	W0115	212R	24		34-45-14	050-099, 150-156, 162-166
	F	A180	2	W0105	657R	24		22-32-11	ALL
	F	A180	2	W0115	657R	24		22-32-11	ALL
	F	A181	2	W0105	658R	24		22-32-11	ALL
	F	A181	2	W0115	658R	24		22-32-11	ALL
	F	A184	2	W0105	663R	24		22-32-12	ALL
	F	A184	2	W0115	663R	24		22-32-12	ALL
	D	C001	2	W0105	125	22		34-12-61	ALL
	F	C003	2	W0105	235B	24		27-32-11	ALL
	F	C003	2	W0125	202B	24		27-32-11	ALL
	F	C036	2	W0105	518B	24		34-12-61	ALL
	F	C036	2	W0125	203B	24		34-12-61	ALL
	F	C054	2	W0105	590B	24		34-45-14	050-099, 150-156, 162-166, 275-276
	F	C054	2	W0115	211B	24		34-45-14	050-099, 150-156, 162-166
	Y	C073	BJ	W0105	546B	24		34-45-14	157, 167-199, 277-299
	Y	C073	BJ	W0105	583B	24		34-45-14	157, 167-199, 277-299
	Y	C073	BJ	W0105	585B	24		34-45-14	157, 167-199, 277-299
	Y	C073	BJ	W0105	588B	24		34-45-14	157, 167-199, 277-299
	Y	C074	BJ	W0105	590B	24		34-45-14	157, 167-199, 277-299
	Y	C074	BJ	W0105	599B	24		34-45-14	157, 167-199, 277-299
	Y	C074	BJ	W0115	211B	24		34-45-14	157, 167-199, 277-299
	F	C075	2	W0105	246B	24		22-33-11	ALL
	F	C075	2	W0115	208B	24		22-33-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 43

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	F	C076	2	W0105	531B	24		22-33-11	ALL
	F	C076	2	W0115	207B	24		22-33-11	ALL
	F	C077	2	W0105	613	24		77-35-11	ALL
	F	C077	2	W0115	603	24		77-35-11	ALL
	F	C079	2	W0105	648B	24		22-32-12	150-199, 275-299
	F	C080	2	W0105	648B	24		22-32-12	050-099
	F	C094	2	W0105	154	24		22-32-13	ALL
	F	C095	2	W0105	156	24		22-32-13	ALL
	F	C105	2	W0105	377B	24		34-12-11	ALL
	F	C105	2	W0115	301B	24		34-12-11	ALL
	F	C117	2	W0105	163	24		22-15-12	ALL
	F	C117	2	W0125	005	24		22-15-12	ALL
	F	C119	2	W0105	065	24		22-15-12	ALL
	F	C119	2	W0115	065	24		22-15-12	ALL
	F	C122	2	W0105	046	22		22-14-11	ALL
	F	C122	2	W0115	046	22		22-14-11	ALL
	F	C124	2	W0105	582B	24		77-12-11	150-157, 275-276
	F	C124	2	W0115	209B	24		77-12-11	150-157, 275-276
	F	C129	2	W0105	209B	24		31-31-12	ALL
	F	C129	2	W0115	201B	24		31-31-12	ALL
	Y	C141	%	W0105	573B	24		31-31-20	150-199, 275-299
	F	C173	2	W0105	312B	24		22-32-12	ALL
	F	C176	2	W0105	592B	24		34-45-14	050-099, 150-156, 162-166, 275-276
	F	C176	2	W0115	212B	24		34-45-14	050-099, 150-156, 162-166
	F	C180	2	W0105	657B	24		22-32-11	ALL
	F	C180	2	W0115	657B	24		22-32-11	ALL
	F	C181	2	W0105	658B	24		22-32-11	ALL
	F	C181	2	W0115	658B	24		22-32-11	ALL
	F	C184	2	W0105	663B	24		22-32-12	ALL
	F	C184	2	W0115	663B	24		22-32-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 44

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	G	CAP	Y	W0105	137	22		34-45-14	157, 167-199, 277-299
	G	CAP	Y	W0105	138	22		34-45-14	157, 167-199, 277-299
	G	CAP	Y	W0105	140	22		34-45-14	157, 167-199, 277-299
	Y	CAP	Y	W0105	573B	24		31-31-20	050-099
	Y	CAP	Y	W0105	573R	24		31-31-20	050-099
	H	CAP	Y	W0105	723	22		22-32-14	050-099
	Z	CAP	Y	W0105	890	24		31-31-19	050-099
	G	CAP	Y	W0115	037	22		34-45-14	157, 167-199, 277-299
	H	DED		W0105	001Z			22-11-12	ALL
	H	DED		W0105	002Z			22-11-12	ALL
	H	DED		W0105	005Z			22-11-12	ALL
	H	DED		W0105	008Z			22-11-12	ALL
	H	DED		W0105	023Z			22-11-12	ALL
	F	DED		W0105	065Z			22-15-12	ALL
	F	DED		W0105	163Z			22-15-12	ALL
	H	DED		W0105	502Z			34-12-11	ALL
	H	DED		W0105	503Z			34-12-11	ALL
	H	DED		W0105	504Z			34-12-11	ALL
	H	DED		W0105	507Z			34-12-11	ALL
	H	DED		W0105	520Z			34-12-61	ALL
	H	DED		W0105	525Z			34-12-61	ALL
	G	DED		W0105	656Z			22-32-11	ALL
	H	DED		W0105	659Z			22-32-11	ALL
	F	DED		W0105	663Z			22-32-12	ALL
	G	DED		W0105	677Z			22-33-11	ALL
	G	DED		W0105	679Z			22-33-11	ALL
	G	DED		W0105	802Z			34-12-11	ALL
	G	DED		W0125	003Z			34-12-11	ALL
	G	DED		W0125	105Z			34-12-11	ALL
	H	DED		W0125	106Z			34-12-11	ALL
	H	DED		W0125	107Z			34-12-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 45

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	H	DED		W0125	205Z			34-12-11	ALL
	H	DED		W0125	206Z			34-12-11	ALL
	G	DED		W0125	709Z			22-31-12	ALL
	G	REF		W0105	546	20		34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	546	20		34-45-14	157, 167-199, 277-299
	G	REF		W0105	546Z			34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	546Z			34-45-14	157, 167-199, 277-299
	G	REF		W0105	568	20		34-45-14	ALL
	G	REF		W0105	568Z			34-45-14	ALL
	G	REF		W0105	583	20		34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	583	20		34-45-14	157, 167-199, 277-299
	G	REF		W0105	583Z			34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	583Z			34-45-14	157, 167-199, 277-299
	G	REF		W0105	585	20		34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	585	20		34-45-14	157, 167-199, 277-299
	G	REF		W0105	585Z			34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	585Z			34-45-14	157, 167-199, 277-299
	G	REF		W0105	588	20		34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	588	20		34-45-14	157, 167-199, 277-299
	G	REF		W0105	588Z			34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	588Z			34-45-14	157, 167-199, 277-299
	Y	REF		W0105	590	20		34-45-14	157, 167-199, 277-299
	Y	REF		W0105	590Z			34-45-14	157, 167-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 46

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0105		284T0384-8 (continued)					SHELF/E01/03		ALL
TB0105	D	BACM15C1A (continued)					SHELF/E01/03		050-099
TB0105	D	DIODEBLOCK-REF284T0113- (continued)					SHELF/E01/03		150-199, 275-299
TB0105	F	BACM15C1A (continued)					SHELF/E01/03		ALL
TB0105	G	BACM15C1B (continued)					SHELF/E01/03		ALL
TB0105	H	BACM15C2A (continued)					SHELF/E01/03		ALL
TB0105	X	BACM15C3A (continued)					SHELF/E01/03		050-099, 275-299
TB0105	Y	BACM15C3B (continued)					SHELF/E01/03		ALL
TB0105	Z	BACM15C3B (continued)					SHELF/E01/03		ALL
	F	REF		W0105	592	20		34-45-14	050-099, 150-156, 162-166, 275-276
	F	REF		W0105	592Z			34-45-14	050-099, 150-156, 162-166, 275-276
	Y	REF		W0105	599	20		34-45-14	157, 167-199, 277-299
	Y	REF		W0105	599Z			34-45-14	157, 167-199, 277-299
	Y	REF		W0115	211	20		34-45-14	157, 167-199, 277-299
	Y	REF		W0115	211Z			34-45-14	157, 167-199, 277-299
	F	REF		W0115	212	20		34-45-14	050-099, 150-156, 162-166
	F	REF		W0115	212Z			34-45-14	050-099, 150-156, 162-166
TB0106		BACT442150U					P061-00/ /		ALL
TB0106	G	BACM15C1B					P061-00/ /		150-199, 275-299
TB0106	X	BACM15C3A					P061-00/ /		ALL
TB0106	Y	BACM15C3B					P061-00/ /		ALL
TB0106	Z	BACM15C3C					P061-00/ /		ALL
	Z	37	BJ	W0062	813	22		33-16-26	ALL
	Z	37	BJ	W0070	06F	22		33-16-22	ALL
	Z	37	BJ	W0070	06L	22		33-16-22	ALL
	Z	38	BJ	W0062	814	22		33-16-26	ALL
	Z	38	BJ	W0070	06J	22		33-16-22	ALL
	Z	38	BJ	W0070	06M	22		33-16-22	ALL
	X	A001	BJ	W0062	664	24		24-32-11	ALL
	X	A001	BJ	W0070	01Y	24		24-32-11	ALL
	X	A005	BJ	W0062	64F	24		80-11-11	ALL
	X	A005	BJ	W0070	10B	24		80-11-11	ALL
	X	A006	BJ	W0062	64G	24		80-11-11	ALL
	X	A006	BJ	W0070	10C	24		80-11-11	ALL
	X	A007	BJ	W0062	64S	24		35-21-11	ALL
	X	A007	BJ	W0070	12S	24		35-21-11	ALL
	Y	A011	BJ	W0062	53G	24		24-51-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 47

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0106		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0106	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	A011	BJ	W0066	53G	24		24-51-31	ALL
	Y	A011	BJ	W0070	02P	24		24-51-31	ALL
	Y	A014	BJ	W0062	771	22		24-25-11	ALL
	Y	A014	BJ	W0066	786	22		24-25-11	ALL
	Y	A014	BJ	W0070	02F	22		24-25-11	ALL
	Y	A018	BJ	W0070	006	22		29-32-11	ALL
	Y	A018	BJ	W0070	04H	22		29-32-11	ALL
	Y	A018	BJ	W0070	04J	22		29-32-11	ALL
	Y	A019	BJ	W0062	70F	20		29-11-14	ALL
	Y	A019	BJ	W0070	020	22		29-11-32	ALL
	Y	A019	BJ	W0070	03W	22		29-11-32	ALL
	Y	A019	BJ	W0070	03X	22		29-11-32	ALL
	Y	A020	BJ	W0070	806R	20		26-23-12	ALL
	Y	A020	BJ	W0070	880R	20		26-23-12	150-199, 275-299
	Y	A020	BJ	W0070	895R	20		26-23-12	ALL
	Y	A020	BJ	W0070	896R	20		26-23-12	ALL
	Y	A021	BJ	W0070	803R	20		26-21-11	ALL
	Y	A021	BJ	W0070	883R	20		26-21-11	ALL
	Y	A021	BJ	W0070	884R	20		26-21-11	ALL
	Y	A022	BJ	W0070	804R	20		26-21-11	ALL
	Y	A022	BJ	W0070	881R	20		26-21-11	ALL
	Y	A022	BJ	W0070	882R	20		26-21-11	ALL
	Y	A023	BJ	W0070	801R	20		26-23-12	150-154
	Y	A023	BJ	W0070	810R	20		26-23-12	150-154
	Y	A023	BJ	W0070	815R	20		26-23-12	150-154
	Y	A024	BJ	W0070	723R	22		26-15-11	ALL
	Y	A024	BJ	W0070	763R	22		26-11-11	ALL
	Y	A024	BJ	W0070	764R	22		26-11-11	ALL
	Y	A024	BJ	W0070	774R	22		26-11-21	ALL
	Y	A025	BJ	W0066	64D	20		78-34-21	155
	Y	A025	BJ	W0070	63R	20		78-34-21	155
	Y	A026	BJ	W0062	778	24		24-31-11	ALL
	Y	A026	BJ	W0070	01V	24		24-31-11	ALL
	Y	A026	BJ	W0070	01W	24		24-31-11	ALL
	Y	A026	BJ	W0070	697	24		24-31-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 48

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0106		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0106	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	A028	BJ	W0066	64D	20		78-34-21	050-099, 150-154, 156-199, 275-299
	Y	A028	BJ	W0070	63R	20		78-34-21	050-099, 150-154, 156-199, 275-299
	Y	A029	BJ	W0065	059	24		31-31-22	ALL
	Y	A029	BJ	W0070	10F	24		80-11-11	ALL
	Y	A029	BJ	W0070	10V	24		80-11-11	ALL
	X	B001	BJ	W0062	682	24		24-32-11	ALL
	X	B001	BJ	W0070	01Z	24		24-32-11	ALL
	X	B003	BJ	W0062	59A	22		SPARE	150-199, 275-299
	X	B003	BJ	W0070	59A	22		SPARE	150-199, 275-299
	X	B004	BJ	W0062	64L	22		33-51-11	ALL
	X	B004	BJ	W0070	676	22		33-51-11	ALL
	X	B005	BJ	W0062	64M	22		33-51-11	ALL
	X	B005	BJ	W0070	666	22		33-51-11	ALL
	X	C003	BJ	W0066	58Z	24		33-51-11	ALL
	X	C003	BJ	W0070	672	24		33-51-11	ALL
	X	C004	BJ	W0066	59A	22		33-51-11	ALL
	X	C004	BJ	W0070	665	22		33-51-11	ALL
	X	C005	BJ	W0066	59C	22		33-51-11	ALL
	X	C005	BJ	W0070	662	22		33-51-11	ALL
	X	C010	BJ	W0066	138	24		21-58-12	ALL
	X	C010	BJ	W0070	13J	24		21-58-12	ALL
	Y	C011	BJ	W0062	53H	24		24-51-31	ALL
	Y	C011	BJ	W0066	53H	24		24-51-31	ALL
	Y	C011	BJ	W0066	53J	24		24-51-31	ALL
	Y	C011	BJ	W0070	02R	24		24-51-31	ALL
	Y	C013	BJ	W0070	50E	24		33-16-11	ALL
	Y	C013	BJ	W0070	636	24		33-16-11	ALL
	Y	C013	BJ	W0070	637	24		33-16-11	ALL
	Y	C014	BJ	W0062	50S	24		21-44-21	275-276
	Y	C014	BJ	W0066	63P	24		21-44-11	ALL
	Y	C014	BJ	W0070	01G	24		21-44-11	ALL
	Y	C014	BJ	W0070	01X	24		21-44-21	275-276
	Y	C017	BJ	W0070	04V	22		32-42-11	ALL
	Y	C017	BJ	W0070	04W	22		32-42-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 49

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0106		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0106	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	Y	C017	BJ	W0070	875	22		32-42-11	ALL
	Y	C020	BJ	W0070	836R	20		26-23-11	ALL
	Y	C020	BJ	W0070	885R	20		26-23-11	ALL
	Y	C020	BJ	W0070	886R	20		26-23-11	ALL
	Y	C021	BJ	W0070	833R	20		26-21-11	ALL
	Y	C021	BJ	W0070	893R	20		26-21-11	ALL
	Y	C021	BJ	W0070	894R	20		26-21-11	ALL
	Y	C022	BJ	W0070	834R	20		26-21-11	ALL
	Y	C022	BJ	W0070	891R	20		26-21-11	ALL
	Y	C022	BJ	W0070	892R	20		26-21-11	ALL
	Y	C023	BJ	W0070	807R	20		26-22-21	ALL
	Y	C023	BJ	W0070	887R	20		26-22-21	ALL
	Y	C023	BJ	W0070	888R	20		26-22-21	ALL
	Y	C023	BJ	W0070	889R	20		26-22-21	ALL
	Y	C024	BJ	W0070	802R	20		26-23-12	150-154
	Y	C024	BJ	W0070	811R	20		26-23-12	150-154
	Y	C024	BJ	W0070	816R	20		26-23-12	150-154
	Y	C025	BJ	W0070	813R	20		26-22-21	275-299
	Y	C025	BJ	W0070	877R	20		26-22-21	275-299
	Y	C025	BJ	W0070	879R	20		26-22-21	275-299
	Y	C026	BJ	W0070	02C	24		24-33-11	ALL
	Y	C026	BJ	W0070	02D	24		24-33-11	ALL
	Y	C026	BJ	W0070	02W	24		24-33-11	ALL
	Y	C026	BJ	W0070	685	24		24-33-11	ALL
	Y	C029	BJ	W0065	060	24		31-31-22	ALL
	Y	C029	BJ	W0070	11F	24		80-11-21	ALL
	Y	C029	BJ	W0070	11V	24		80-11-21	ALL
	Y	CAP	Y	W0062	50S	24		SPARE	051-099, 150-154
	Y	CAP	Y	W0070	01X	24		SPARE	051-099, 150-154
	X	D001	BJ	W0066	209B	24		28-41-11	ALL
	X	D001	BJ	W0070	209B	24		28-41-11	ALL
	X	D002	BJ	W0066	209R	24		28-41-11	ALL
	X	D002	BJ	W0070	209R	24		28-41-11	ALL
	X	D004	BJ	W0066	64M	22		33-51-11	ALL
	X	D004	BJ	W0070	674	22		33-51-11	ALL
	X	D005	BJ	W0066	64L	22		33-51-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 50

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0106		<b>BACT442150U (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P061-00/ /</b>		<b>150-199, 275-299</b>
TB0106	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
TB0106	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P061-00/ /</b>		<b>ALL</b>
	X	D005	BJ	W0070	663	22		33-51-11	ALL
	X	D010	BJ	W0062	143	22		21-58-16	ALL
	X	D010	BJ	W0070	13P	22		21-58-16	ALL
	X	DED		W0062	143Z			21-58-16	ALL
	Y	DED		W0062	53GZ			24-51-31	ALL
	Y	DED		W0062	53HZ			24-51-31	ALL
	X	DED		W0062	64FZ			80-11-11	ALL
	X	DED		W0062	64GZ			80-11-11	ALL
	Y	DED		W0062	771Z			24-25-11	ALL
	Z	DED		W0062	813Z			33-16-26	ALL
	Z	DED		W0062	814Z			33-16-26	ALL
	Y	DED		W0066	53GZ			24-51-31	ALL
	Y	DED		W0066	53HZ			24-51-31	ALL
	Y	DED		W0066	53JZ			24-51-31	ALL
	Y	DED		W0066	786Z			24-25-11	ALL
	X	DED		W0070	10BZ			80-11-11	ALL
	X	DED		W0070	10CZ			80-11-11	ALL
	Y	DED		W0070	10FZ			80-11-11	ALL
	Y	DED		W0070	10VZ			80-11-11	ALL
TB0108		<b>MTB16E103-43A</b>					<b>P028-00/ /</b>		<b>ALL</b>
TB0108	<b>L</b>	<b>MRTB16E03-225</b>					<b>P028-00/ /</b>		<b>ALL</b>
TB0108	<b>M</b>	<b>MRTB16E04-225</b>					<b>P028-00/ /</b>		<b>ALL</b>
	M	1	1	W1056	022	18		28-41-11	ALL
	M	1	1	W1056	024	18		28-41-11	ALL
	M	1	1	W1056	026	18		28-41-11	ALL
	M	1	1	W1056	036	18		28-21-13	ALL
	M	1	1	W1056	065	18		28-21-12	ALL
	M	1	1	W1056	067	18		28-21-12	ALL
	M	1	1	W1056	068	18		28-21-12	ALL
	M	3	1	W1056	023	18		28-41-12	ALL
	M	3	1	W1056	025	18		28-41-12	ALL
	M	3	1	W1056	027	18		28-41-12	ALL
	M	3	1	W1056	069	18		28-41-12	ALL
	L	6	1	W1056	052	18		28-21-13	ALL
	L	6	1	W1056	058	18		28-21-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 51

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0108		MTB16E103-43A (continued)					P028-00/ /		ALL
TB0108	L	MRTB16E03-225 (continued)					P028-00/ /		ALL
TB0108	M	MRTB16E04-225 (continued)					P028-00/ /		ALL
	L	6	1	W1056	070	18		28-21-11	ALL
TB0110		BACT44B1775U					P035-00/ /		050-099
TB0110	D	DIODEBLOCK-REF284T0687-					P035-00/ /		ALL
TB0110	G	BACM15C1B					P035-00/ /		ALL
TB0110	H	BACM15C2A					P035-00/ /		ALL
TB0110	Y	BACM15C3B					P035-00/ /		150-199, 275-299
TB0110	Z	BACM15C3C					P035-00/ /		ALL
	G	1	2	W1066	516	22		25-53-13	050-099
	Z	1	BJ	W1066	516	22		25-53-13	150-199, 275-299
	G	1	2	W1066	550	22		25-53-13	050-099
	Z	1	BJ	W1066	550	22		25-53-13	150-199, 275-299
	G	1	2	W1066	648	22		25-53-13	050-099
	Z	1	BJ	W1066	648	22		25-53-13	150-199, 275-299
	G	1	2	W1066	668	22		25-53-13	050-099
	Z	1	BJ	W1066	879	22		25-53-13	150-199, 275-299
	H	10	2	W1066	01S	22		25-53-13	150-199, 275-299
	H	10	2	W1066	669	22		25-53-13	150-199, 275-299
	H	10	2	W1066	679	22		25-53-13	150-199, 275-299
	H	10	2	W1066	763	22		25-53-13	150-199, 275-299
	H	10	2	W1066	769	22		25-53-13	150-199, 275-299
	H	12	2	W1066	04Q	22		25-53-13	150-199, 275-299
	H	12	2	W1066	04R	22		25-53-13	150-199, 275-299
	H	12	2	W1066	558	22		25-53-13	150-199, 275-299
	G	13	2	W1066	03X	22		25-53-16	050-099
	G	13	2	W1066	504	22		25-53-13	050-099
	G	13	2	W1066	848	22		25-53-13	050-099
	H	14	2	W1066	600	22		25-53-14	050-099
	Z	14	BJ	W1066	600	22		25-53-14	150-199, 275-299
	H	14	2	W1066	610	22		25-53-14	050-099
	Z	14	BJ	W1066	610	22		25-53-14	150-199, 275-299
	Z	14	BJ	W1066	620	22		25-53-14	150-199, 275-299
	Z	14	BJ	W1066	630	22		25-53-14	150-199, 275-299
	H	14	2	W1066	714	22		25-53-14	050-099
	H	14	2	W1066	730	22		25-53-14	050-099
	Z	14	BJ	W1066	730	22		25-53-14	150-199, 275-299
	H	14	2	W1066	750	22		25-53-14	050-099
	Z	14	BJ	W1066	750	22		25-53-14	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 52

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	H	14	2	W1066	752	22		25-53-14	050-099
	Z	14	BJ	W1066	752	22		25-53-14	150-199, 275-299
	H	14	2	W1066	872	22		25-53-14	050-099
	Z	14	BJ	W1066	872	22		25-53-14	150-199, 275-299
	Z	15	BJ	W1066	198	22		25-53-14	150-199, 275-299
	Z	15	BJ	W1066	730	22		25-53-14	150-199, 275-299
	Z	15	BJ	W1066	786	22		25-53-14	150-199, 275-299
	Z	15	BJ	W1066	796	22		25-53-14	150-199, 275-299
	H	16	2	W1066	01A	22		25-53-13	150-199, 275-299
	H	16	2	W1066	01B	22		25-53-13	150-199, 275-299
	H	16	2	W1066	01G	22		25-53-13	150-199, 275-299
	H	16	2	W1066	01H	22		25-53-13	150-199, 275-299
	H	16	2	W1066	01U	22		25-53-13	150-199, 275-299
	H	16	2	W1066	04D	22		25-53-16	150-199, 275-299
	H	16	2	W1066	04U	22		25-53-15	150-199, 275-299
	H	16	2	W1066	624	22		25-53-14	050-099
	H	16	2	W1066	665	22		25-53-14	050-099
	H	16	2	W1066	730	22		25-53-14	050-099
	H	16	2	W1066	775	22		25-53-14	050-099
	H	16	2	W1066	786	22		25-53-14	050-099
	H	16	2	W1066	796	22		25-53-14	050-099
	Z	18	BJ	W1066	34E	22		25-53-14	150-199, 275-299
	H	18	2	W1066	625	22		25-53-14	050-099
	Z	18	BJ	W1066	720	22		25-53-14	150-199, 275-299
	Z	18	BJ	W1066	736	22		25-53-14	150-199, 275-299
	H	18	2	W1066	746	22		25-53-14	050-099
	Z	18	BJ	W1066	746	22		25-53-14	150-199, 275-299
	H	18	2	W1066	748	22		25-53-14	050-099
	Z	18	BJ	W1066	780	22		25-53-14	150-199, 275-299
	Z	18	BJ	W1066	782	22		25-53-14	150-199, 275-299
	Z	18	BJ	W1066	875	22		25-53-14	150-199, 275-299
	Z	19	BJ	W1066	33X	22		25-53-14	150-199, 275-299
	Z	19	BJ	W1066	34S	22		25-53-14	150-199, 275-299
	Z	19	BJ	W1066	34W	22		25-53-14	150-199, 275-299
	Z	19	BJ	W1066	762	22		25-53-14	150-199, 275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 53

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	19	BJ	W1066	766	22		25-53-14	150-199, 275-299
	G	2	2	W1066	517	22		25-53-13	050-099
	Z	2	BJ	W1066	517	22		25-53-13	150-199, 275-299
	G	2	2	W1066	552	22		25-53-13	050-099
	Z	2	BJ	W1066	552	22		25-53-13	150-199, 275-299
	G	2	2	W1066	658	22		25-53-13	050-099
	Z	2	BJ	W1066	658	22		25-53-13	150-199, 275-299
	G	2	2	W1066	687	22		25-53-13	050-099
	Z	2	BJ	W1066	878	22		25-53-13	150-199, 275-299
	H	20	2	W1066	545	22		25-53-14	050-099
	H	20	2	W1066	682	22		25-53-14	050-099
	Z	20	BJ	W1066	692	22		25-53-14	150-199, 275-299
	Z	20	BJ	W1066	702	22		25-53-14	150-199, 275-299
	H	20	2	W1066	710	22		25-53-14	050-099
	H	20	2	W1066	731	22		25-53-14	050-099
	H	20	2	W1066	766	22		25-53-14	050-099
	H	20	2	W1066	768	22		25-53-14	050-099
	Z	20	BJ	W1066	787	22		25-53-14	150-199, 275-299
	H	20	2	W1066	889	22		25-53-14	050-099
	H	20	2	W1066	894	22		25-53-14	050-099
	Z	21	BJ	W1066	010	22		25-53-13	150-199, 275-299
	Z	21	BJ	W1066	32D	22		25-53-13	150-199, 275-299
	Z	21	BJ	W1066	629	22		25-53-13	150-199, 275-299
	Z	21	BJ	W1066	639	22		25-53-13	150-199, 275-299
	Z	21	BJ	W1066	749	22		25-53-13	150-199, 275-299
	G	22	2	W1066	01V	22		25-53-14	150-199, 275-299
	G	22	2	W1066	602	22		25-53-14	ALL
	G	22	2	W1066	612	22		25-53-14	ALL
	G	22	2	W1066	737	22		25-53-14	ALL
	G	22	2	W1066	807	22		25-53-14	050-099
	G	23	2	W1066	870	22		25-53-14	ALL
	G	23	2	W1066	871	22		25-53-14	ALL
	G	23	2	W1066	874	22		25-53-14	ALL
	G	24	2	W1066	01X	22		25-53-14	150-199, 275-299
	G	24	2	W1066	622	22		25-53-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 54

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	G	24	2	W1066	632	22		25-53-14	ALL
	G	24	2	W1066	738	22		25-53-14	050-099
	G	24	2	W1066	747	22		25-53-14	ALL
	G	25	2	W1066	640	22		25-53-14	ALL
	G	25	2	W1066	650	22		25-53-14	ALL
	G	25	2	W1066	751	22		25-53-14	ALL
	G	26	2	W1066	03L	22		25-53-16	150-199, 275-299
	G	26	2	W1066	04B	22		25-53-16	050-099
	G	26	2	W1066	04H	22		25-53-16	150-199, 275-299
	G	26	2	W1066	515	22		25-53-14	050-099
	G	26	2	W1066	754	22		25-53-16	150-199, 275-299
	G	26	2	W1066	847	22		25-53-14	050-099
	G	26	2	W1066	877	22		25-53-14	150-199, 275-299
	G	27	2	W1066	620	22		25-53-14	050-099
	Z	27	BJ	W1066	660	22		25-53-14	150-199, 275-299
	Z	27	BJ	W1066	670	22		25-53-14	150-199, 275-299
	G	27	2	W1066	686	22		25-53-14	050-099
	G	27	2	W1066	696	22		25-53-14	050-099
	Z	27	BJ	W1066	761	22		25-53-14	150-199, 275-299
	Z	27	BJ	W1066	788	22		25-53-14	150-199, 275-299
	Z	27	BJ	W1066	798	22		25-53-14	150-199, 275-299
	Z	27	BJ	W1066	898	22		25-53-14	150-199, 275-299
	G	28	2	W1066	662	22		25-53-14	050-099
	Z	28	BJ	W1066	662	22		25-53-14	150-199, 275-299
	G	28	2	W1066	672	22		25-53-14	050-099
	Z	28	BJ	W1066	672	22		25-53-14	150-199, 275-299
	G	28	2	W1066	767	22		25-53-14	050-099
	Z	28	BJ	W1066	767	22		25-53-14	150-199, 275-299
	G	29	2	W1066	03D	22		25-53-16	150-199, 275-299
	G	29	2	W1066	03G	22		25-53-16	150-199, 275-299
	G	29	2	W1066	04P	22		25-53-16	150-199, 275-299
	G	29	2	W1066	540	22		25-53-14	050-099
	G	29	2	W1066	630	22		25-53-14	050-099
	G	29	2	W1066	685	22		25-53-14	050-099
	G	3	2	W1066	551	22		25-53-13	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 55

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	G	3	2	W1066	608	22		25-53-13	150-199, 275-299
	G	3	2	W1066	625	22		25-53-14	050-099
	G	3	2	W1066	628	22		25-53-13	150-199, 275-299
	G	3	2	W1066	731	22		25-53-14	050-099
	G	3	2	W1066	736	22		25-53-14	050-099
	G	3	2	W1066	875	22		25-53-14	050-099
	G	30	2	W1066	03U	22		25-53-16	050-099
	G	30	2	W1066	513	22		25-53-13	050-099
	G	30	2	W1066	677	22		25-53-14	150-199, 275-299
	G	30	2	W1066	685	22		25-53-14	150-199, 275-299
	G	30	2	W1066	686	22		25-53-14	150-199, 275-299
	G	30	2	W1066	776	22		25-53-13	050-099
	G	30	2	W1066	885	22		25-53-13	050-099
	G	31	2	W1066	545	22		25-53-14	050-099
	G	31	2	W1066	690	22		25-53-14	ALL
	G	31	2	W1066	700	22		25-53-14	ALL
	G	31	2	W1066	720	22		25-53-14	050-099
	G	31	2	W1066	781	22		25-53-14	150-199, 275-299
	G	32	2	W1066	01K	22		25-53-13	150-199, 275-299
	G	32	2	W1066	01M	22		25-53-13	150-199, 275-299
	G	32	2	W1066	03U	22		25-53-16	150-199, 275-299
	G	32	2	W1066	513	22		25-53-13	150-199, 275-299
	G	32	2	W1066	549	22		25-53-14	050-099
	G	32	2	W1066	692	22		25-53-14	050-099
	G	32	2	W1066	702	22		25-53-14	050-099
	G	32	2	W1066	787	22		25-53-14	050-099
	Z	33	BJ	W1066	196	22		25-53-14	150-199, 275-299
	Z	33	BJ	W1066	34T	22		25-53-14	150-199, 275-299
	Z	33	BJ	W1066	35A	22		25-53-14	150-199, 275-299
	G	33	2	W1066	547	22		25-53-14	050-099
	G	33	2	W1066	712	22		25-53-14	050-099
	Z	33	BJ	W1066	712	22		25-53-14	150-199, 275-299
	G	33	2	W1066	722	22		25-53-14	050-099
	Z	33	BJ	W1066	722	22		25-53-14	150-199, 275-299
	G	33	2	W1066	797	22		25-53-14	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 56

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	D	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	G	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	H	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	Y	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	Z	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	33	BJ	W1066	797	22		25-53-14	150-199, 275-299
	Z	34	BJ	W1066	02D	22		25-53-14	150-199, 275-299
	Z	34	BJ	W1066	02E	22		25-53-14	150-199, 275-299
	Z	34	BJ	W1066	02N	22		25-53-14	150-199, 275-299
	Z	35	BJ	W1066	33H	22		25-53-13	150-199, 275-299
	Z	35	BJ	W1066	33M	22		25-53-13	150-199, 275-299
	G	35	2	W1066	539	22		25-53-13	050-099
	Z	35	BJ	W1066	539	22		25-53-13	150-199, 275-299
	G	35	2	W1066	698	22		25-53-13	050-099
	Z	35	BJ	W1066	698	22		25-53-13	150-199, 275-299
	G	35	2	W1066	718	22		25-53-13	050-099
	Z	35	BJ	W1066	718	22		25-53-13	150-199, 275-299
	Z	36	BJ	W1066	33F	22		25-53-13	150-199, 275-299
	Z	36	BJ	W1066	33K	22		25-53-13	150-199, 275-299
	G	36	2	W1066	560	22		25-53-13	050-099
	Z	36	BJ	W1066	560	22		25-53-13	150-199, 275-299
	G	36	2	W1066	708	22		25-53-13	050-099
	Z	36	BJ	W1066	708	22		25-53-13	150-199, 275-299
	G	36	2	W1066	728	22		25-53-13	050-099
	Z	36	BJ	W1066	728	22		25-53-13	150-199, 275-299
	Z	37	BJ	W1066	642	22		25-53-14	150-199, 275-299
	Z	37	BJ	W1066	652	22		25-53-14	150-199, 275-299
	Z	37	BJ	W1066	757	22		25-53-14	150-199, 275-299
	Z	37	BJ	W1066	896	22		25-53-14	150-199, 275-299
	G	38	2	W1066	03D	22		25-53-16	050-099
	Z	38	BJ	W1066	03E	22		25-53-16	150-199, 275-299
	G	38	2	W1066	03G	22		25-53-16	050-099
	G	38	2	W1066	04P	22		25-53-16	050-099
	Z	38	BJ	W1066	05A	22		25-53-13	150-199, 275-299
	Z	38	BJ	W1066	05D	22		25-53-17	150-199, 275-299
	Z	38	BJ	W1066	578	22		25-53-16	150-199, 275-299
	Z	38	BJ	W1066	579	22		25-53-16	150-199, 275-299
	Z	39	BJ	W1066	01C	22		25-53-13	150-199, 275-299
	H	39	2	W1066	01F	22		25-53-14	050-099
	Z	39	BJ	W1066	01N	22		25-53-13	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 57

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	39	BJ	W1066	177	22		25-53-13	150-199, 275-299
	H	39	2	W1066	198	22		25-53-14	050-099
	Z	39	BJ	W1066	32C	22		25-53-13	150-199, 275-299
	Z	39	BJ	W1066	37T	22		25-53-13	150-199, 275-299
	Z	39	BJ	W1066	500	22		25-53-13	150-199, 275-299
	Z	39	BJ	W1066	530	22		25-53-13	150-199, 275-299
	H	39	2	W1066	531	22		25-53-13	050-099
	Z	39	BJ	W1066	531	22		25-53-13	150-199, 275-299
	H	39	2	W1066	559	22		25-53-13	050-099
	H	39	2	W1066	573	22		25-53-15	050-099
	H	39	2	W1066	580	22		25-53-13	050-099
	H	39	2	W1066	583	22		25-53-15	050-099
	H	39	2	W1066	596	20		33-37-11	050-099
	G	4	2	W1066	553	22		25-53-13	ALL
	G	4	2	W1066	618	22		25-53-13	ALL
	G	4	2	W1066	638	22		25-53-13	ALL
	Z	40	BJ	W1066	47C	22		25-53-17	150-199, 275-299
	Z	40	BJ	W1066	48C	22		25-53-17	150-199, 275-299
	Z	40	BJ	W1066	49C	22		25-53-17	150-199, 275-299
	Z	40	BJ	W1066	531	22		25-53-13	150-199, 275-299
	Z	40	BJ	W1066	554	22		25-53-13	150-199, 275-299
	Z	40	BJ	W1066	559	22		25-53-13	150-199, 275-299
	Z	40	BJ	W1066	580	22		25-53-13	150-199, 275-299
	Z	40	BJ	W1066	596	20		33-37-11	150-199, 275-299
	Z	41	BJ	W1066	01L	22		25-53-13	150-199, 275-299
	Z	41	BJ	W1066	34B	22		25-53-14	150-199, 275-299
	Z	41	BJ	W1066	532	22		25-53-13	150-199, 275-299
	Z	41	BJ	W1066	576	22		25-53-15	150-199, 275-299
	Z	41	BJ	W1066	580	22		25-53-13	150-199, 275-299
	Z	41	BJ	W1066	586	22		25-53-15	150-199, 275-299
	H	41	2	W1066	669	22		25-53-13	050-099
	H	41	2	W1066	679	22		25-53-13	050-099
	H	41	2	W1066	763	22		25-53-13	050-099
	H	41	2	W1066	769	22		25-53-13	050-099
	H	41	2	W1066	809	22		25-53-13	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 58

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	41	BJ	W1066	873	22		25-53-14	150-199, 275-299
	Z	41	BJ	W1066	876	22		25-53-14	150-199, 275-299
	Z	42	BJ	W1066	02U	22		25-53-14	150-199, 275-299
	Z	42	BJ	W1066	03R	22		25-53-16	150-199, 275-299
	Z	42	BJ	W1066	05A	22		25-53-13	150-199, 275-299
	Z	42	BJ	W1066	532	22		25-53-13	150-199, 275-299
	Z	42	BJ	W1066	689	22		25-53-13	150-199, 275-299
	Z	43	BJ	W1066	02B	22		25-53-14	150-199, 275-299
	Z	43	BJ	W1066	02L	22		25-53-14	150-199, 275-299
	H	43	2	W1066	03B	22		25-53-16	050-099
	Z	43	BJ	W1066	03B	22		25-53-14	150-199, 275-299
	Z	43	BJ	W1066	04T	22		25-53-14	150-199, 275-299
	Z	43	BJ	W1066	178	22		25-53-14	150-199, 275-299
	Z	43	BJ	W1066	34K	22		25-53-14	150-199, 275-299
	H	43	2	W1066	535	22		25-53-14	050-099
	H	43	2	W1066	614	22		25-53-14	050-099
	H	43	2	W1066	664	22		25-53-14	050-099
	H	43	2	W1066	684	22		25-53-14	050-099
	H	43	2	W1066	793	22		25-53-14	050-099
	Z	43	BJ	W1066	793	22		25-53-14	150-199, 275-299
	H	43	2	W1066	823	22		25-53-14	050-099
	Z	44	BJ	W1066	03M	22		25-53-16	150-199, 275-299
	Z	44	BJ	W1066	04G	22		25-53-16	150-199, 275-299
	Z	44	BJ	W1066	37G	22		25-53-16	150-199, 275-299
	G	45	2	W1066	141	20		52-34-11	ALL
	G	45	2	W1066	151	20		52-34-11	ALL
	G	45	2	W1066	161	20		52-34-11	ALL
	G	46	2	W1066	142	20		52-34-11	ALL
	G	46	2	W1066	152	20		52-34-11	ALL
	G	46	2	W1066	162	20		52-34-11	ALL
	G	47	2	W1066	143	20		52-34-11	ALL
	G	47	2	W1066	153	20		52-34-11	ALL
	G	47	2	W1066	163	20		52-34-11	ALL
	G	48	2	W1066	803	24		52-34-12	ALL
	G	48	2	W1066	819	24		52-34-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 59

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	G	48	2	W1066	824	24		52-34-12	ALL
	G	48	2	W1066	828	24		52-34-12	ALL
	G	49	2	W1066	802	24		52-34-12	ALL
	G	49	2	W1066	821	24		52-34-12	ALL
	G	49	2	W1066	825	24		52-34-12	ALL
	G	49	2	W1066	829	24		52-34-12	ALL
	G	5	2	W1066	523	24		52-34-12	150-199, 275-299
	G	5	2	W1066	556	22		25-53-15	050-099
	G	5	2	W1066	574	22		25-53-15	050-099
	G	5	2	W1066	577	22		25-53-15	050-099
	G	5	2	W1066	804	24		52-34-12	150-199, 275-299
	G	5	2	W1066	814	24		52-34-12	150-199, 275-299
	Z	50	BJ	W1066	01D	22		25-53-13	150-199, 275-299
	Z	50	BJ	W1066	01E	22		25-53-13	150-199, 275-299
	Z	50	BJ	W1066	01F	22		25-53-13	150-199, 275-299
	Z	50	BJ	W1066	50C	22		25-53-17	150-199, 275-299
	H	50	2	W1066	571	22		25-53-13	050-099
	H	50	2	W1066	580	22		25-53-13	050-099
	H	50	2	W1066	581	22		25-53-13	050-099
	Z	50	BJ	W1066	649	22		25-53-13	150-199, 275-299
	Z	50	BJ	W1066	659	22		25-53-13	150-199, 275-299
	H	50	2	W1066	678	22		25-53-13	050-099
	H	50	2	W1066	689	22		25-53-13	050-099
	Z	50	BJ	W1066	753	22		25-53-13	150-199, 275-299
	Z	50	BJ	W1066	759	22		25-53-13	150-199, 275-299
	H	50	2	W1066	873	22		25-53-14	050-099
	H	50	2	W1066	876	22		25-53-14	050-099
	Z	51	BJ	W1066	01P	22		25-53-13	150-199, 275-299
	Z	51	BJ	W1066	01Q	22		25-53-13	150-199, 275-299
	Z	51	BJ	W1066	783	22		25-53-13	150-199, 275-299
	Z	51	BJ	W1066	789	22		25-53-13	150-199, 275-299
	Z	51	BJ	W1066	799	22		25-53-13	150-199, 275-299
	H	52	2	W1066	548	22		25-53-13	050-099
	H	52	2	W1066	629	22		25-53-13	050-099
	H	52	2	W1066	639	22		25-53-13	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 60

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	D	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	G	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	H	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	Y	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	Z	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	H	52	2	W1066	677	22		25-53-13	050-099
	H	52	2	W1066	774	22		25-53-13	050-099
	H	52	2	W1066	777	22		25-53-13	050-099
	H	54	2	W1066	551	22		25-53-13	050-099
	H	54	2	W1066	608	22		25-53-13	050-099
	H	54	2	W1066	628	22		25-53-13	050-099
	Z	6	BJ	W1066	34D	22		25-53-14	150-199, 275-299
	Z	6	BJ	W1066	756	22		25-53-14	150-199, 275-299
	Z	6	BJ	W1066	758	22		25-53-14	150-199, 275-299
	Z	6	BJ	W1066	760	22		25-53-14	150-199, 275-299
	Z	6	BJ	W1066	768	22		25-53-14	150-199, 275-299
	Z	7	BJ	W1066	04X	22		25-53-14	150-199, 275-299
	Z	7	BJ	W1066	34E	22		25-53-14	150-199, 275-299
	Z	7	BJ	W1066	34N	22		25-53-14	150-199, 275-299
	Z	7	BJ	W1066	34R	22		25-53-14	150-199, 275-299
	Z	7	BJ	W1066	35C	22		25-53-14	150-199, 275-299
	Z	7	BJ	W1066	35F	22		25-53-14	150-199, 275-299
	G	7	2	W1066	555	22		25-53-13	050-099
	G	7	2	W1066	572	22		25-53-13	050-099
	Z	7	BJ	W1066	748	22		25-53-14	150-199, 275-299
	G	7	2	W1066	777	22		25-53-13	050-099
	G	8	2	W1066	32D	22		25-53-13	150-199, 275-299
	G	8	2	W1066	32E	22		25-53-13	150-199, 275-299
	G	8	2	W1066	555	22		25-53-13	150-199, 275-299
	Z	8	BJ	W1066	649	22		25-53-13	050-099
	Z	8	BJ	W1066	659	22		25-53-13	050-099
	Z	8	BJ	W1066	697	22		25-53-13	050-099
	Z	8	BJ	W1066	753	22		25-53-13	050-099
	Z	8	BJ	W1066	810	22		25-53-13	050-099
	Z	8	BJ	W1066	892	22		25-53-13	050-099
	G	9	2	W1066	33E	22		25-53-13	150-199, 275-299
	G	9	2	W1066	33P	22		25-53-13	150-199, 275-299
	G	9	2	W1066	33S	22		25-53-13	150-199, 275-299
	G	9	2	W1066	33T	22		25-53-13	150-199, 275-299
	Z	9	BJ	W1066	624	22		25-53-14	050-099

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 61

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0110		<b>BACT44B1775U (continued)</b>					<b>P035-00/ /</b>		<b>050-099</b>
TB0110	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0110	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0110	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	9	BJ	W1066	680	22		25-53-14	050-099
	Z	9	BJ	W1066	760	22		25-53-14	050-099
	Z	9	BJ	W1066	762	22		25-53-14	050-099
	D	A006	2	W1066	50D	22		25-53-13	050-099
	D	A010	2	W1066	898	22		25-53-14	050-099
	D	A011	2	W1066	896	22		25-53-14	050-099
	D	A012	2	W1066	699	22		25-53-13	050-099
	D	A034	2	W1066	719	22		25-53-13	050-099
	D	A037	2	W1066	609	22		25-53-13	050-099
	Y	A052	BJ	W1066	02P	22		25-53-14	150-199, 275-299
	Y	A052	BJ	W1066	02Q	22		25-53-14	150-199, 275-299
	Y	A052	BJ	W1066	665	22		25-53-14	150-199, 275-299
	Y	A053	BJ	W1066	03X	22		25-53-16	150-199, 275-299
	Y	A053	BJ	W1066	504	22		25-53-13	150-199, 275-299
	Y	A053	BJ	W1066	848	22		25-53-13	150-199, 275-299
	D	C006	2	W1066	50J	22		25-53-16	050-099
	D	C010	2	W1066	897	22		25-53-14	050-099
	D	C011	2	W1066	895	22		25-53-14	050-099
	D	C011	2	W1066	897	22		25-53-14	050-099
	D	C012	2	W1066	564	22		25-53-13	050-099
	D	C012	2	W1066	789	22		25-53-13	050-099
	D	C034	2	W1066	146	22		25-53-13	050-099
	D	C034	2	W1066	799	22		25-53-13	050-099
	D	C037	2	W1066	019	22		25-53-13	050-099
	D	C037	2	W1066	543	22		25-53-13	050-099
	Y	C052	BJ	W1066	02H	22		25-53-14	150-199, 275-299
	Y	C052	BJ	W1066	02K	22		25-53-14	150-199, 275-299
	Y	C052	BJ	W1066	684	22		25-53-14	150-199, 275-299
	Y	C053	BJ	W1066	02S	22		25-53-14	150-199, 275-299
	Y	C053	BJ	W1066	02T	22		25-53-14	150-199, 275-299
	Y	C053	BJ	W1066	02X	22		25-53-14	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 62

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0112		BACT44B1050U					P035-00/ /		ALL
TB0112	D	YHLZD-30					P035-00/ /		ALL
TB0112	G	BACM15C1B					P035-00/ /		ALL
TB0112	H	BACM15C2A					P035-00/ /		ALL
TB0112	Y	BACM15C3B					P035-00/ /		ALL
TB0112	Z	BACM15C3C					P035-00/ /		ALL
	H	1	2	W1066	092	22		25-53-16	050-099
	Z	1	BJ	W1066	092	22		25-53-16	150-199, 275-299
	H	1	2	W1066	093	22		25-53-16	050-099
	Z	1	BJ	W1066	093	22		25-53-16	150-199, 275-299
	H	1	2	W1066	094	22		25-53-16	050-099
	Z	1	BJ	W1066	094	22		25-53-16	150-199, 275-299
	H	1	2	W1066	095	22		25-53-16	050-099
	Z	1	BJ	W1066	095	22		25-53-16	150-199, 275-299
	H	1	2	W1066	096	22		25-53-17	050-099
	Z	1	BJ	W1066	096	22		25-53-17	150-199, 275-299
	H	1	2	W1066	39A	22		25-53-16	050-099
	Z	1	BJ	W1066	39A	22		25-53-16	150-199, 275-299
	H	1	2	W1066	644	20		25-53-17	050-099
	Z	1	BJ	W1066	644	22		25-53-17	150-199, 275-299
	Z	10	BJ	W1066	32J	22		25-53-13	150-199, 275-299
	Z	10	BJ	W1066	33W	22		25-53-14	150-199, 275-299
	Z	10	BJ	W1066	34A	22		25-53-14	150-199, 275-299
	Z	10	BJ	W1066	34C	22		25-53-14	150-199, 275-299
	Z	10	BJ	W1066	547	22		25-53-13	150-199, 275-299
	Z	10	BJ	W1066	567	22		25-53-13	150-199, 275-299
	Z	10	BJ	W1066	568	22		25-53-13	150-199, 275-299
	G	11	2	W1066	519	22		25-53-14	050-099
	G	11	2	W1066	520	22		25-53-14	050-099
	G	11	2	W1066	815	22		25-53-14	050-099
	G	13	2	W1066	114	22		25-53-16	150-199, 275-299
	G	13	2	W1066	131	22		25-53-16	150-199, 275-299
	G	13	2	W1066	132	22		25-53-16	150-199, 275-299
	G	14	2	W1066	116	22		25-53-16	ALL
	G	14	2	W1066	134	22		25-53-16	ALL
	G	14	2	W1066	135	22		25-53-16	ALL
	H	15	2	W1066	832	20		26-16-21	ALL
	H	15	2	W1066	838	20		26-16-21	ALL
	H	15	2	W1066	840	20		26-16-21	ALL
	H	15	2	W1066	844	20		26-16-21	ALL
	H	15	2	W1066	852	20		26-16-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 63

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0112		<b>BACT44B1050U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	H	15	2	W1066	860	20		26-16-21	ALL
	H	15	2	W1066	864	20		26-16-21	ALL
	G	17	2	W1066	179	20		26-16-21	ALL
	G	17	2	W1066	180	20		26-16-21	ALL
	G	17	2	W1066	190	20		26-16-21	ALL
	G	19	2	W1066	830	20		26-16-21	ALL
	G	19	2	W1066	833	20		26-16-21	ALL
	G	19	2	W1066	845	20		26-16-21	ALL
	Z	2	BJ	W1066	096	22		25-53-17	150-199, 275-299
	Z	2	BJ	W1066	097	22		25-53-17	150-199, 275-299
	Z	2	BJ	W1066	098	22		25-53-17	150-199, 275-299
	Z	2	BJ	W1066	099	22		25-53-17	150-199, 275-299
	Z	2	BJ	W1066	100	22		25-53-17	150-199, 275-299
	G	20	2	W1066	044	18		33-37-11	ALL
	G	20	2	W1066	046	18		33-37-11	ALL
	G	20	2	W1066	064	18		33-37-11	050-099
	G	20	2	W1066	064	16		33-37-11	150-199, 275-299
	G	21	2	W1066	850	20		26-16-21	ALL
	G	21	2	W1066	853	20		26-16-21	ALL
	G	21	2	W1066	865	20		26-16-21	ALL
	H	23	2	W1066	831	20		26-16-21	ALL
	H	23	2	W1066	835	20		26-16-21	ALL
	H	23	2	W1066	839	20		26-16-21	ALL
	H	23	2	W1066	851	20		26-16-21	ALL
	H	23	2	W1066	855	20		26-16-21	ALL
	Z	25	BJ	W1066	03A	22		25-53-14	150-199, 275-299
	Z	25	BJ	W1066	04B	22		25-53-16	150-199, 275-299
	Z	25	BJ	W1066	34F	22		25-53-14	150-199, 275-299
	Z	25	BJ	W1066	35X	22		25-53-14	150-199, 275-299
	Z	25	BJ	W1066	682	22		25-53-14	150-199, 275-299
	Z	26	BJ	W1066	03E	22		25-53-16	050-099
	Z	26	BJ	W1066	03R	22		25-53-16	050-099
	Z	26	BJ	W1066	03V	22		25-53-16	050-099
	Z	26	BJ	W1066	03W	22		25-53-16	050-099
	Z	26	BJ	W1066	04A	22		25-53-16	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 64

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0112		<b>BACT44B1050U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	26	BJ	W1066	04T	22		25-53-16	050-099
	Z	26	BJ	W1066	189	22		25-53-14	150-199, 275-299
	Z	26	BJ	W1066	34G	22		25-53-14	150-199, 275-299
	Z	26	BJ	W1066	35Y	22		25-53-14	150-199, 275-299
	Z	26	BJ	W1066	680	22		25-53-14	150-199, 275-299
	Z	26	BJ	W1066	857	22		25-53-16	050-099
	Z	27	BJ	W1066	007	22		25-53-13	050-099
	G	27	2	W1066	05D	22		25-53-17	150-199, 275-299
	Z	27	BJ	W1066	199	22		25-53-14	050-099
	Z	27	BJ	W1066	50D	22		25-53-13	050-099
	Z	27	BJ	W1066	50H	22		25-53-15	050-099
	G	27	2	W1066	597	22		25-53-17	150-199, 275-299
	G	27	2	W1066	598	22		25-53-17	150-199, 275-299
	Z	27	BJ	W1066	676	22		25-53-13	050-099
	Z	27	BJ	W1066	779	22		25-53-13	050-099
	Z	27	BJ	W1066	780	22		25-53-13	050-099
	G	27	2	W1066	888	22		25-53-17	150-199, 275-299
	G	28	2	W1066	32A	20		25-53-11	150-199, 275-299
	G	28	2	W1066	590	20		25-53-11	150-199, 275-299
	G	28	2	W1066	868	20		25-53-11	150-199, 275-299
	G	28	2	W1066	869	20		25-53-11	150-199, 275-299
	H	3	2	W1066	096	22		25-53-17	050-099
	H	3	2	W1066	097	22		25-53-17	050-099
	H	3	2	W1066	098	22		25-53-17	050-099
	H	3	2	W1066	099	22		25-53-17	050-099
	H	3	2	W1066	100	22		25-53-17	050-099
	G	31	2	W1066	647	22		25-53-17	ALL
	G	31	2	W1066	654	22		25-53-17	ALL
	G	31	2	W1066	880	22		25-53-17	ALL
	G	32	2	W1066	37P	22		25-53-17	ALL
	G	32	2	W1066	508	22		25-53-17	ALL
	G	32	2	W1066	704	22		25-53-17	ALL
	G	32	2	W1066	705	22		25-53-17	ALL
	G	33	2	W1066	637	22		25-53-17	ALL
	G	33	2	W1066	656	22		25-53-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 65

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0112		<b>BACT44B1050U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	G	33	2	W1066	888	20		25-53-17	050-099
	G	33	2	W1066	888	22		25-53-17	150-199, 275-299
	Z	34	BJ	W1066	34H	22		25-53-14	150-199, 275-299
	Z	34	BJ	W1066	35S	22		25-53-15	150-199, 275-299
	Z	34	BJ	W1066	518	22		25-53-14	150-199, 275-299
	G	34	2	W1066	590	20		25-53-11	050-099
	G	34	2	W1066	868	20		25-53-11	050-099
	G	34	2	W1066	869	20		25-53-11	050-099
	H	35	2	W1066	660	22		25-53-14	050-099
	H	35	2	W1066	670	22		25-53-14	050-099
	H	35	2	W1066	761	22		25-53-14	050-099
	H	35	2	W1066	788	22		25-53-14	050-099
	H	35	2	W1066	798	22		25-53-14	050-099
	H	35	2	W1066	898	22		25-53-14	050-099
	Z	5	BJ	W1066	255	22		25-53-11	150-199, 275-299
	Z	5	BJ	W1066	37B	22		25-53-15	150-199, 275-299
	Z	5	BJ	W1066	37E	22		25-53-15	150-199, 275-299
	Z	5	BJ	W1066	37V	22		25-53-16	150-199, 275-299
	Z	5	BJ	W1066	501	22		25-53-11	150-199, 275-299
	H	5	2	W1066	532	22		25-53-13	050-099
	H	5	2	W1066	576	22		25-53-15	050-099
	H	5	2	W1066	578	22		25-53-16	050-099
	H	5	2	W1066	579	22		25-53-16	050-099
	H	5	2	W1066	586	22		25-53-15	050-099
	H	5	2	W1066	597	22		25-53-17	050-099
	H	5	2	W1066	598	22		25-53-17	050-099
	H	5	2	W1066	888	20		25-53-17	050-099
	Z	5	BJ	W1066	893	22		25-53-11	150-199, 275-299
	Z	6	BJ	W1066	199	22		25-53-14	150-199, 275-299
	Z	6	BJ	W1066	34P	22		25-53-14	150-199, 275-299
	Z	6	BJ	W1066	34X	22		25-53-14	150-199, 275-299
	Z	6	BJ	W1066	35B	22		25-53-14	150-199, 275-299
	H	7	2	W1066	071	22		25-53-15	050-099
	Z	7	BJ	W1066	071	22		25-53-15	150-199, 275-299
	H	7	2	W1066	072	22		25-53-15	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 66

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0112		<b>BACT44B1050U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	7	BJ	W1066	072	22		25-53-15	150-199, 275-299
	H	7	2	W1066	073	22		25-53-15	050-099
	Z	7	BJ	W1066	073	22		25-53-15	150-199, 275-299
	H	7	2	W1066	081	22		25-53-15	050-099
	Z	7	BJ	W1066	081	22		25-53-15	150-199, 275-299
	H	7	2	W1066	082	22		25-53-15	050-099
	Z	7	BJ	W1066	082	22		25-53-15	150-199, 275-299
	H	7	2	W1066	083	22		25-53-15	050-099
	Z	7	BJ	W1066	083	22		25-53-15	150-199, 275-299
	H	7	2	W1066	38A	22		25-53-15	050-099
	Z	7	BJ	W1066	38A	22		25-53-15	150-199, 275-299
	Z	8	BJ	W1066	534	22		25-53-17	150-199, 275-299
	Z	8	BJ	W1066	635	22		25-53-17	150-199, 275-299
	Z	8	BJ	W1066	636	22		25-53-17	150-199, 275-299
	Z	8	BJ	W1066	644	22		25-53-17	150-199, 275-299
	Z	8	BJ	W1066	655	22		25-53-17	150-199, 275-299
	Z	9	BJ	W1066	503	20		25-53-11	150-199, 275-299
	Z	9	BJ	W1066	521	20		25-53-11	150-199, 275-299
	H	9	2	W1066	534	22		25-53-17	050-099
	Z	9	BJ	W1066	537	20		33-37-11	150-199, 275-299
	Z	9	BJ	W1066	589	20		25-53-11	150-199, 275-299
	Z	9	BJ	W1066	593	20		25-53-11	150-199, 275-299
	Z	9	BJ	W1066	594	20		33-37-11	150-199, 275-299
	H	9	2	W1066	635	22		25-53-17	050-099
	H	9	2	W1066	636	22		25-53-17	050-099
	H	9	2	W1066	644	20		25-53-17	050-099
	H	9	2	W1066	655	22		25-53-17	050-099
	D	A003	2	W1066	33L	22		25-53-13	150-199, 275-299
	D	A004	2	W1066	877	22		25-53-14	150-199, 275-299
	Y	A012	BJ	W1066	03M	22		25-53-16	050-099
	Y	A012	BJ	W1066	04G	22		25-53-16	050-099
	Y	A012	BJ	W1066	04L	22		25-53-14	150-199, 275-299
	Y	A012	BJ	W1066	35D	22		25-53-14	150-199, 275-299
	Y	A012	BJ	W1066	35E	22		25-53-14	150-199, 275-299
	Y	A012	BJ	W1066	35R	22		25-53-14	150-199, 275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 67

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0112		<b>BACT44B1050U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Y	A012	BJ	W1066	37G	22		25-53-16	050-099
	Y	A013	BJ	W1066	04A	22		25-53-16	050-099
	Y	A013	BJ	W1066	514	22		25-53-14	050-099
	Y	A013	BJ	W1066	800	22		25-53-14	050-099
	D	A018	2	W1066	04D	22		25-53-16	150-199, 275-299
	D	A018	2	W1066	887	22		25-53-16	050-099
	D	A022	2	W1066	04K	22		25-53-16	ALL
	D	A022	2	W1066	754	22		25-53-16	150-199, 275-299
	D	A022	2	W1066	795	22		25-53-16	050-099
	D	A025	2	W1066	50H	22		25-53-15	050-099
	D	A028	2	W1066	557	22		25-53-15	050-099
	Y	A029	BJ	W1066	507	22		25-53-14	050-099
	Y	A029	BJ	W1066	509	22		25-53-14	050-099
	Y	A029	BJ	W1066	707	22		25-53-14	050-099
	D	A029	2	W1066	878	22		25-53-13	150-199, 275-299
	Y	A030	BJ	W1066	604	22		25-53-14	050-099
	Y	A030	BJ	W1066	642	22		25-53-14	050-099
	Y	A030	BJ	W1066	652	22		25-53-14	050-099
	D	A030	2	W1066	879	22		25-53-13	150-199, 275-299
	Y	A030	BJ	W1066	896	22		25-53-14	050-099
	D	C003	2	W1066	33D	22		25-53-13	150-199, 275-299
	D	C003	2	W1066	35W	22		25-53-13	150-199, 275-299
	D	C004	2	W1066	04M	22		25-53-14	150-199, 275-299
	D	C004	2	W1066	04N	22		25-53-14	150-199, 275-299
	Y	C011	BJ	W1066	34L	22		25-53-14	150-199, 275-299
	Y	C011	BJ	W1066	34M	22		25-53-14	150-199, 275-299
	Y	C011	BJ	W1066	710	22		25-53-14	150-199, 275-299
	Y	C012	BJ	W1066	02K	22		25-53-16	050-099
	Y	C012	BJ	W1066	716	22		25-53-14	050-099
	Y	C012	BJ	W1066	849	22		25-53-14	050-099
	Y	C013	BJ	W1066	114	22		25-53-16	050-099
	Y	C013	BJ	W1066	131	22		25-53-16	050-099
	Y	C013	BJ	W1066	132	22		25-53-16	050-099
	D	C018	2	W1066	04C	22		25-53-16	150-199, 275-299
	D	C018	2	W1066	04M	22		25-53-16	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 68

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0112		<b>BACT44B1050U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0112	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	D	C018	2	W1066	04N	22		25-53-16	050-099
	D	C022	2	W1066	04J	22		25-53-16	ALL
	D	C025	2	W1066	50F	22		25-53-15	050-099
	D	C025	2	W1066	587	22		25-53-15	050-099
	D	C028	2	W1066	50F	22		25-53-15	050-099
	D	C028	2	W1066	584	22		25-53-15	050-099
	Y	C029	BJ	W1066	510	22		25-53-14	050-099
	Y	C029	BJ	W1066	512	22		25-53-14	050-099
	D	C029	2	W1066	678	22		25-53-13	150-199, 275-299
	Y	C029	BJ	W1066	706	22		25-53-14	050-099
	Y	C030	BJ	W1066	605	22		25-53-14	050-099
	Y	C030	BJ	W1066	606	22		25-53-14	050-099
	D	C030	2	W1066	668	22		25-53-13	150-199, 275-299
	Y	C030	BJ	W1066	715	22		25-53-14	050-099
	Y	C030	BJ	W1066	894	22		25-53-14	050-099
TB0114		<b>BACT44B0510U</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>D</b>	<b>DIODEBLOCK-REF284T0687-</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>F</b>	<b>BACM15C1A</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0114	<b>G</b>	<b>BACM15C1B</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>H</b>	<b>BACM15C2A</b>					<b>P035-00/ /</b>		<b>ALL</b>
	H	1	2	W1066	503	20		25-53-11	050-099
	H	1	2	W1066	521	20		25-53-11	050-099
	H	1	2	W1066	537	20		33-37-11	050-099
	H	1	2	W1066	589	20		25-53-11	050-099
	H	1	2	W1066	593	20		25-53-11	050-099
	H	1	2	W1066	594	20		33-37-11	050-099
	H	3	2	W1066	37B	22		25-53-15	050-099
	H	3	2	W1066	37E	22		25-53-15	050-099
	H	3	2	W1066	37V	22		25-53-16	050-099
	H	3	2	W1066	501	22		25-53-11	050-099
	H	3	2	W1066	542	22		25-53-11	050-099
	H	3	2	W1066	883	22		25-53-15	050-099
	H	3	2	W1066	884	22		25-53-15	050-099

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 69

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0114		<b>BACT44B0510U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0114	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	H	3	2	W1066	893	22		25-53-11	050-099
	H	5	2	W1066	37T	22		25-53-13	050-099
	H	5	2	W1066	530	22		25-53-13	050-099
	H	5	2	W1066	531	22		25-53-13	050-099
	H	5	2	W1066	532	22		25-53-13	050-099
	H	5	2	W1066	566	22		25-53-13	050-099
	H	5	2	W1066	778	22		25-53-13	050-099
	H	5	2	W1066	782	22		25-53-13	050-099
	H	5	2	W1066	857	22		25-53-16	050-099
	G	7	2	W1066	523	24		52-34-12	050-099
	G	7	2	W1066	804	24		52-34-12	050-099
	G	7	2	W1066	818	24		52-34-12	050-099
	D	A	2	W1066	619	22		25-53-13	050-099
	D	A	2	W1066	709	22		25-53-13	050-099
	D	A	2	W1066	729	22		25-53-13	050-099
	D	A	2	W1066	890	20		25-53-11	050-099
	D	A001	2	W1066	807	24		52-34-12	150-199, 275-299
	D	A002	2	W1066	599	20		25-53-11	150-199, 275-299
	D	A003	2	W1066	619	22		25-53-13	150-199, 275-299
	D	A004	2	W1066	609	22		25-53-13	150-199, 275-299
	D	A005	2	W1066	04U	22		25-53-15	150-199, 275-299
	D	A006	2	W1066	557	22		25-53-15	150-199, 275-299
	D	A007	2	W1066	709	22		25-53-13	150-199, 275-299
	D	A008	2	W1066	699	22		25-53-13	150-199, 275-299
	D	A009	2	W1066	898	22		25-53-14	150-199, 275-299
	D	A010	2	W1066	896	22		25-53-14	150-199, 275-299
	D	A011	2	W1066	719	22		25-53-13	150-199, 275-299
	D	A012	2	W1066	729	22		25-53-13	150-199, 275-299
	D	A013	2	W1066	33J	22		25-53-13	150-199, 275-299
	D	A014	2	W1066	33G	22		25-53-13	150-199, 275-299
	D	A015	2	W1066	33N	22		25-53-13	150-199, 275-299
	D	C	2	W1066	009	22		25-53-13	050-099
	D	C	2	W1066	010	22		25-53-13	050-099
	D	C	2	W1066	019	22		25-53-13	050-099
	D	C	2	W1066	522	20		25-53-11	050-099
	D	C001	2	W1066	527	24		52-34-12	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 70

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0114		<b>BACT44B0510U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P035-00/ /</b>		<b>150-199, 275-299</b>
TB0114	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0114	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	D	C002	2	W1066	522	20		25-53-11	150-199, 275-299
	D	C003	2	W1066	009	22		25-53-13	150-199, 275-299
	D	C003	2	W1066	540	22		25-53-13	150-199, 275-299
	D	C004	2	W1066	540	22		25-53-13	150-199, 275-299
	D	C004	2	W1066	739	22		25-53-13	150-199, 275-299
	D	C005	2	W1066	04V	22		25-53-15	150-199, 275-299
	D	C006	2	W1066	04V	22		25-53-15	150-199, 275-299
	D	C006	2	W1066	04W	22		25-53-15	150-199, 275-299
	D	C007	2	W1066	01R	22		25-53-13	150-199, 275-299
	D	C008	2	W1066	01Q	22		25-53-13	150-199, 275-299
	D	C008	2	W1066	01R	22		25-53-13	150-199, 275-299
	D	C009	2	W1066	897	22		25-53-14	150-199, 275-299
	D	C010	2	W1066	895	22		25-53-14	150-199, 275-299
	D	C010	2	W1066	897	22		25-53-14	150-199, 275-299
	D	C011	2	W1066	019	22		25-53-13	150-199, 275-299
	D	C012	2	W1066	019	22		25-53-13	150-199, 275-299
	D	C012	2	W1066	32N	22		25-53-13	150-199, 275-299
	D	C013	2	W1066	33T	22		25-53-13	150-199, 275-299
	D	C014	2	W1066	33S	22		25-53-13	150-199, 275-299
	D	C015	2	W1066	33D	22		25-53-13	150-199, 275-299
	D	C015	2	W1066	33R	22		25-53-13	150-199, 275-299
TB0118		<b>BACT44B1775U</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688-</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C</b>					<b>P039-00/ /</b>		<b>ALL</b>
	G	1	2	W1068	516	22		25-53-23	ALL
	G	1	2	W1068	550	22		25-53-23	ALL
	G	1	2	W1068	668	22		25-53-23	ALL
	Z	10	BJ	W1068	32E	22		25-53-23	150-199, 275-299
	Z	10	BJ	W1068	33D	22		25-53-23	150-199, 275-299
	Z	10	BJ	W1068	33T	22		25-53-23	150-199, 275-299
	H	10	2	W1068	554	22		25-53-23	050-099
	Z	10	BJ	W1068	555	22		25-53-23	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 71

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	H	10	2	W1068	669	22		25-53-23	050-099
	H	10	2	W1068	679	22		25-53-23	050-099
	Z	10	BJ	W1068	739	22		25-53-23	150-199, 275-299
	Z	10	BJ	W1068	749	22		25-53-23	150-199, 275-299
	Z	10	BJ	W1068	753	22		25-53-23	150-199, 275-299
	Z	10	BJ	W1068	759	22		25-53-23	150-199, 275-299
	H	10	2	W1068	763	22		25-53-23	050-099
	H	10	2	W1068	769	22		25-53-23	050-099
	Z	11	BJ	W1068	33T	22		25-53-23	150-199, 275-299
	Z	11	BJ	W1068	34A	22		25-53-23	150-199, 275-299
	Z	11	BJ	W1068	699	22		25-53-23	150-199, 275-299
	Z	11	BJ	W1068	709	22		25-53-23	150-199, 275-299
	Z	11	BJ	W1068	763	22		25-53-23	150-199, 275-299
	Z	11	BJ	W1068	769	22		25-53-23	150-199, 275-299
	Z	12	BJ	W1068	34D	22		25-53-23	150-199, 275-299
	Z	12	BJ	W1068	34G	22		25-53-23	150-199, 275-299
	Z	12	BJ	W1068	34H	22		25-53-23	150-199, 275-299
	Z	12	BJ	W1068	34L	22		25-53-23	150-199, 275-299
	H	12	2	W1068	558	22		25-53-23	050-099
	Z	12	BJ	W1068	558	22		25-53-23	150-199, 275-299
	H	12	2	W1068	582	22		25-53-23	050-099
	H	12	2	W1068	699	22		25-53-23	050-099
	H	12	2	W1068	709	22		25-53-23	050-099
	H	12	2	W1068	789	22		25-53-23	050-099
	Z	13	BJ	W1068	35B	22		25-53-24	150-199, 275-299
	Z	13	BJ	W1068	35D	22		25-53-24	150-199, 275-299
	Z	13	BJ	W1068	35G	22		25-53-24	150-199, 275-299
	Z	13	BJ	W1068	35J	22		25-53-24	150-199, 275-299
	Z	13	BJ	W1068	758	22		25-53-24	150-199, 275-299
	Z	14	BJ	W1068	35K	22		25-53-24	150-199, 275-299
	Z	14	BJ	W1068	35L	22		25-53-24	150-199, 275-299
	H	14	2	W1068	600	22		25-53-24	050-099
	Z	14	BJ	W1068	600	22		25-53-24	150-199, 275-299
	H	14	2	W1068	610	22		25-53-24	050-099
	Z	14	BJ	W1068	610	22		25-53-24	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 72

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	H	14	2	W1068	620	22		25-53-24	050-099
	Z	14	BJ	W1068	620	22		25-53-24	150-199, 275-299
	H	14	2	W1068	630	22		25-53-24	050-099
	Z	14	BJ	W1068	630	22		25-53-24	150-199, 275-299
	H	14	2	W1068	730	22		25-53-24	050-099
	Z	14	BJ	W1068	730	22		25-53-24	150-199, 275-299
	H	14	2	W1068	750	22		25-53-24	050-099
	Z	14	BJ	W1068	750	22		25-53-24	150-199, 275-299
	H	14	2	W1068	752	22		25-53-24	050-099
	H	14	2	W1068	872	22		25-53-24	050-099
	Z	15	BJ	W1068	37G	22		25-53-26	150-199, 275-299
	Z	15	BJ	W1068	707	22		25-53-26	150-199, 275-299
	Z	15	BJ	W1068	836	22		25-53-26	150-199, 275-299
	Z	16	BJ	W1068	34W	22		25-53-24	150-199, 275-299
	Z	16	BJ	W1068	34X	22		25-53-24	150-199, 275-299
	H	16	2	W1068	680	22		25-53-24	050-099
	H	16	2	W1068	730	22		25-53-24	050-099
	H	16	2	W1068	760	22		25-53-24	050-099
	Z	16	BJ	W1068	760	22		25-53-24	150-199, 275-299
	H	16	2	W1068	762	22		25-53-24	050-099
	Z	16	BJ	W1068	762	22		25-53-24	150-199, 275-299
	H	16	2	W1068	786	22		25-53-24	050-099
	Z	16	BJ	W1068	786	22		25-53-24	150-199, 275-299
	H	16	2	W1068	788	22		25-53-24	050-099
	Z	16	BJ	W1068	788	22		25-53-24	150-199, 275-299
	Z	16	BJ	W1068	872	22		25-53-24	150-199, 275-299
	Z	17	BJ	W1068	149	22		25-53-23	150-199, 275-299
	Z	17	BJ	W1068	504	22		25-53-23	150-199, 275-299
	Z	17	BJ	W1068	838	22		25-53-26	150-199, 275-299
	Z	18	BJ	W1068	35R	22		25-53-24	150-199, 275-299
	H	18	2	W1068	731	22		25-53-24	050-099
	H	18	2	W1068	736	22		25-53-24	050-099
	Z	18	BJ	W1068	736	22		25-53-24	150-199, 275-299
	H	18	2	W1068	746	22		25-53-24	050-099
	Z	18	BJ	W1068	746	22		25-53-24	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 73

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	H	18	2	W1068	756	22		25-53-24	050-099
	Z	18	BJ	W1068	756	22		25-53-24	150-199, 275-299
	H	18	2	W1068	758	22		25-53-24	050-099
	H	18	2	W1068	875	22		25-53-24	050-099
	Z	18	BJ	W1068	875	22		25-53-24	150-199, 275-299
	Z	19	BJ	W1068	642	22		25-53-24	150-199, 275-299
	Z	19	BJ	W1068	652	22		25-53-24	150-199, 275-299
	Z	19	BJ	W1068	738	22		25-53-24	150-199, 275-299
	Z	19	BJ	W1068	748	22		25-53-24	150-199, 275-299
	Z	19	BJ	W1068	757	22		25-53-24	150-199, 275-299
	G	2	2	W1068	517	22		25-53-23	ALL
	G	2	2	W1068	552	22		25-53-23	ALL
	G	2	2	W1068	678	22		25-53-23	ALL
	Z	20	BJ	W1068	35E	22		25-53-24	150-199, 275-299
	Z	20	BJ	W1068	35F	22		25-53-24	150-199, 275-299
	Z	20	BJ	W1068	584	22		25-53-24	150-199, 275-299
	H	20	2	W1068	682	22		25-53-24	050-099
	H	20	2	W1068	690	22		25-53-24	050-099
	Z	20	BJ	W1068	690	22		25-53-24	150-199, 275-299
	H	20	2	W1068	700	22		25-53-24	050-099
	Z	20	BJ	W1068	700	22		25-53-24	150-199, 275-299
	H	20	2	W1068	731	22		25-53-24	050-099
	H	20	2	W1068	766	22		25-53-24	050-099
	Z	20	BJ	W1068	766	22		25-53-24	150-199, 275-299
	H	20	2	W1068	768	22		25-53-24	050-099
	Z	20	BJ	W1068	768	22		25-53-24	150-199, 275-299
	Z	21	BJ	W1068	32B	22		25-53-24	150-199, 275-299
	Z	21	BJ	W1068	32C	22		25-53-23	150-199, 275-299
	Z	21	BJ	W1068	32F	22		25-53-23	150-199, 275-299
	Z	21	BJ	W1068	34R	22		25-53-24	150-199, 275-299
	Z	21	BJ	W1068	34T	22		25-53-24	150-199, 275-299
	G	22	2	W1068	602	22		25-53-24	ALL
	G	22	2	W1068	612	22		25-53-24	ALL
	G	22	2	W1068	737	22		25-53-24	ALL
	G	23	2	W1068	727	22		25-53-26	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 74

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	G	23	2	W1068	728	22		25-53-26	150-199, 275-299
	G	23	2	W1068	754	22		25-53-26	150-199, 275-299
	G	23	2	W1068	870	22		25-53-24	050-099
	G	23	2	W1068	871	22		25-53-24	050-099
	G	23	2	W1068	874	22		25-53-24	050-099
	G	24	2	W1068	622	22		25-53-24	ALL
	G	24	2	W1068	632	22		25-53-24	ALL
	G	24	2	W1068	747	22		25-53-24	ALL
	G	25	2	W1068	640	22		25-53-24	ALL
	G	25	2	W1068	650	22		25-53-24	ALL
	G	25	2	W1068	751	22		25-53-24	ALL
	G	26	2	W1068	642	22		25-53-24	050-099
	G	26	2	W1068	652	22		25-53-24	050-099
	G	26	2	W1068	741	22		25-53-24	050-099
	G	26	2	W1068	757	22		25-53-24	050-099
	G	27	2	W1068	660	22		25-53-24	ALL
	G	27	2	W1068	670	22		25-53-24	ALL
	G	27	2	W1068	761	22		25-53-24	ALL
	G	28	2	W1068	662	22		25-53-24	ALL
	G	28	2	W1068	672	22		25-53-24	ALL
	G	28	2	W1068	767	22		25-53-24	ALL
	G	29	2	W1068	738	22		25-53-24	050-099
	G	29	2	W1068	741	22		25-53-24	050-099
	G	29	2	W1068	748	22		25-53-24	050-099
	Z	3	BJ	W1068	33N	22		25-53-23	150-199, 275-299
	Z	3	BJ	W1068	34E	22		25-53-23	150-199, 275-299
	G	3	2	W1068	551	22		25-53-23	050-099
	Z	3	BJ	W1068	551	22		25-53-23	150-199, 275-299
	G	3	2	W1068	608	22		25-53-23	050-099
	Z	3	BJ	W1068	608	22		25-53-23	150-199, 275-299
	G	3	2	W1068	628	22		25-53-23	050-099
	Z	3	BJ	W1068	628	22		25-53-23	150-199, 275-299
	G	3	2	W1068	648	22		25-53-23	050-099
	Z	3	BJ	W1068	648	22		25-53-23	150-199, 275-299
	H	30	2	W1068	664	22		25-53-24	050-099

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 75

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	G	30	2	W1068	665	22		25-53-24	150-199, 275-299
	G	30	2	W1068	675	22		25-53-24	150-199, 275-299
	H	30	2	W1068	681	22		25-53-24	050-099
	G	30	2	W1068	685	22		25-53-24	150-199, 275-299
	H	30	2	W1068	775	22		25-53-24	050-099
	G	31	2	W1068	33W	22		25-53-23	150-199, 275-299
	G	31	2	W1068	870	22		25-53-24	150-199, 275-299
	G	31	2	W1068	871	22		25-53-24	150-199, 275-299
	G	31	2	W1068	874	22		25-53-24	150-199, 275-299
	G	32	2	W1068	692	22		25-53-24	ALL
	G	32	2	W1068	702	22		25-53-24	ALL
	G	32	2	W1068	787	22		25-53-24	ALL
	Z	33	BJ	W1068	193	22		25-53-26	150-199, 275-299
	Z	33	BJ	W1068	37B	22		25-53-25	150-199, 275-299
	Z	33	BJ	W1068	37E	22		25-53-25	150-199, 275-299
	Z	33	BJ	W1068	37V	22		25-53-26	150-199, 275-299
	Z	33	BJ	W1068	501	22		25-53-21	150-199, 275-299
	G	33	2	W1068	665	22		25-53-24	050-099
	G	33	2	W1068	675	22		25-53-24	050-099
	G	33	2	W1068	685	22		25-53-24	050-099
	Z	33	BJ	W1068	887	22		25-53-21	150-199, 275-299
	Z	34	BJ	W1068	183	22		25-53-23	150-199, 275-299
	Z	34	BJ	W1068	513	22		25-53-23	150-199, 275-299
	Z	34	BJ	W1068	833	22		25-53-26	150-199, 275-299
	Z	35	BJ	W1068	503	20		25-53-21	150-199, 275-299
	Z	35	BJ	W1068	521	20		25-53-21	150-199, 275-299
	Z	35	BJ	W1068	537	20		33-37-21	150-199, 275-299
	Z	35	BJ	W1068	589	20		25-53-21	150-199, 275-299
	Z	35	BJ	W1068	593	20		25-53-21	150-199, 275-299
	Z	35	BJ	W1068	594	20		33-37-21	150-199, 275-299
	Z	36	BJ	W1068	170	22		25-53-26	150-199, 275-299
	Z	36	BJ	W1068	189	22		25-53-26	150-199, 275-299
	Z	36	BJ	W1068	190	22		25-53-26	150-199, 275-299
	Z	36	BJ	W1068	729	22		25-53-26	150-199, 275-299
	Z	36	BJ	W1068	834	22		25-53-26	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 76

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	Z	36	BJ	W1068	837	22		25-53-26	150-199, 275-299
	G	37	2	W1068	35M	22		25-53-24	150-199, 275-299
	G	37	2	W1068	35N	22		25-53-24	150-199, 275-299
	G	37	2	W1068	35W	22		25-53-24	150-199, 275-299
	G	38	2	W1068	35P	22		25-53-24	150-199, 275-299
	G	38	2	W1068	35T	22		25-53-24	150-199, 275-299
	G	38	2	W1068	35X	22		25-53-24	150-199, 275-299
	Z	39	BJ	W1068	170	22		25-53-26	150-199, 275-299
	Z	39	BJ	W1068	33C	22		25-53-23	150-199, 275-299
	H	39	2	W1068	531	22		25-53-23	050-099
	Z	39	BJ	W1068	531	22		25-53-23	150-199, 275-299
	H	39	2	W1068	559	22		25-53-23	050-099
	Z	39	BJ	W1068	559	22		25-53-23	150-199, 275-299
	H	39	2	W1068	573	22		25-53-25	050-099
	H	39	2	W1068	580	22		25-53-23	050-099
	H	39	2	W1068	583	22		25-53-25	050-099
	H	39	2	W1068	596	20		33-37-21	050-099
	Z	39	BJ	W1068	596	20		33-37-21	150-199, 275-299
	H	39	2	W1068	823	24		52-35-12	050-099
	Z	39	BJ	W1068	823	24		52-35-12	150-199, 275-299
	Z	4	BJ	W1068	33L	22		25-53-23	150-199, 275-299
	Z	4	BJ	W1068	34B	22		25-53-23	150-199, 275-299
	G	4	2	W1068	553	22		25-53-23	050-099
	Z	4	BJ	W1068	553	22		25-53-23	150-199, 275-299
	G	4	2	W1068	618	22		25-53-23	050-099
	Z	4	BJ	W1068	618	22		25-53-23	150-199, 275-299
	G	4	2	W1068	638	22		25-53-23	050-099
	Z	4	BJ	W1068	638	22		25-53-23	150-199, 275-299
	G	4	2	W1068	658	22		25-53-23	050-099
	Z	4	BJ	W1068	658	22		25-53-23	150-199, 275-299
	Z	40	BJ	W1068	34J	22		25-53-23	150-199, 275-299
	Z	40	BJ	W1068	34K	22		25-53-23	150-199, 275-299
	Z	40	BJ	W1068	37T	22		25-53-23	150-199, 275-299
	Z	40	BJ	W1068	530	22		25-53-23	150-199, 275-299
	Z	40	BJ	W1068	531	22		25-53-23	150-199, 275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 77

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	Z	40	BJ	W1068	532	22		25-53-23	150-199, 275-299
	Z	40	BJ	W1068	574	22		25-53-24	150-199, 275-299
	Z	41	BJ	W1068	170	22		25-53-26	050-099
	Z	41	BJ	W1068	189	22		25-53-26	050-099
	Z	41	BJ	W1068	532	22		25-53-23	150-199, 275-299
	Z	41	BJ	W1068	576	22		25-53-25	150-199, 275-299
	Z	41	BJ	W1068	578	22		25-53-26	150-199, 275-299
	Z	41	BJ	W1068	579	22		25-53-26	150-199, 275-299
	Z	41	BJ	W1068	580	22		25-53-23	150-199, 275-299
	Z	41	BJ	W1068	586	22		25-53-25	150-199, 275-299
	Z	41	BJ	W1068	729	22		25-53-26	050-099
	Z	41	BJ	W1068	834	22		25-53-26	050-099
	Z	41	BJ	W1068	837	22		25-53-26	050-099
	Z	41	BJ	W1068	849	22		25-53-26	050-099
	Z	41	BJ	W1068	873	22		25-53-24	150-199, 275-299
	Z	41	BJ	W1068	876	22		25-53-24	150-199, 275-299
	Z	42	BJ	W1068	34M	22		25-53-23	150-199, 275-299
	Z	42	BJ	W1068	34P	22		25-53-23	150-199, 275-299
	Z	42	BJ	W1068	580	22		25-53-23	150-199, 275-299
	Z	42	BJ	W1068	669	22		25-53-23	150-199, 275-299
	Z	42	BJ	W1068	679	22		25-53-23	150-199, 275-299
	Z	42	BJ	W1068	689	22		25-53-23	150-199, 275-299
	G	43	2	W1068	36H	22		25-53-24	150-199, 275-299
	H	43	2	W1068	535	22		25-53-24	050-099
	G	43	2	W1068	535	22		25-53-24	150-199, 275-299
	H	43	2	W1068	676	22		25-53-24	050-099
	H	43	2	W1068	774	22		25-53-24	050-099
	G	43	2	W1068	774	22		25-53-24	150-199, 275-299
	H	43	2	W1068	827	22		25-53-26	050-099
	G	43	2	W1068	827	22		25-53-26	150-199, 275-299
	G	44	2	W1068	805	24		52-35-12	150-199, 275-299
	G	44	2	W1068	816	24		52-35-12	150-199, 275-299
	G	44	2	W1068	822	24		52-35-12	150-199, 275-299
	G	45	2	W1068	144	20		52-35-11	ALL
	G	45	2	W1068	151	20		52-35-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 78

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	G	45	2	W1068	161	20		52-35-11	ALL
	G	46	2	W1068	145	20		52-35-11	ALL
	G	46	2	W1068	152	20		52-35-11	ALL
	G	46	2	W1068	162	20		52-35-11	ALL
	G	47	2	W1068	146	20		52-35-11	ALL
	G	47	2	W1068	153	20		52-35-11	ALL
	G	47	2	W1068	163	20		52-35-11	ALL
	G	48	2	W1068	803	24		52-35-12	ALL
	G	48	2	W1068	819	24		52-35-12	ALL
	G	48	2	W1068	824	24		52-35-12	ALL
	G	48	2	W1068	828	24		52-35-12	ALL
	G	49	2	W1068	802	24		52-35-12	ALL
	G	49	2	W1068	821	24		52-35-12	ALL
	G	49	2	W1068	825	24		52-35-12	ALL
	G	49	2	W1068	829	24		52-35-12	ALL
	G	5	2	W1068	34Y	22		25-53-24	150-199, 275-299
	G	5	2	W1068	35A	22		25-53-24	150-199, 275-299
	G	5	2	W1068	35H	22		25-53-24	150-199, 275-299
	G	5	2	W1068	556	22		25-53-25	050-099
	G	5	2	W1068	574	22		25-53-25	050-099
	G	5	2	W1068	577	22		25-53-25	050-099
	G	50	2	W1068	523	24		52-35-12	150-199, 275-299
	H	50	2	W1068	571	22		25-53-23	050-099
	H	50	2	W1068	580	22		25-53-23	050-099
	H	50	2	W1068	581	22		25-53-23	050-099
	H	50	2	W1068	689	22		25-53-23	050-099
	G	50	2	W1068	804	24		52-35-12	150-199, 275-299
	G	50	2	W1068	814	24		52-35-12	150-199, 275-299
	H	50	2	W1068	873	22		25-53-24	050-099
	H	50	2	W1068	876	22		25-53-24	050-099
	Z	51	BJ	W1068	184	22		25-53-24	150-199, 275-299
	Z	51	BJ	W1068	194	22		25-53-26	150-199, 275-299
	Z	51	BJ	W1068	684	22		25-53-24	150-199, 275-299
	Z	52	BJ	W1068	188	22		25-53-26	150-199, 275-299
	Z	52	BJ	W1068	37J	22		25-53-26	150-199, 275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 79

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	Z	52	BJ	W1068	37L	22		25-53-26	150-199, 275-299
	Z	52	BJ	W1068	46G	22		25-53-26	150-199, 275-299
	Z	52	BJ	W1068	806	22		25-53-26	150-199, 275-299
	G	54	2	W1068	664	22		25-53-24	150-199, 275-299
	G	54	2	W1068	681	22		25-53-24	150-199, 275-299
	G	54	2	W1068	775	22		25-53-24	150-199, 275-299
	G	55	2	W1068	181	22		25-53-26	150-199, 275-299
	G	55	2	W1068	37K	22		25-53-26	150-199, 275-299
	G	55	2	W1068	44G	22		25-53-26	150-199, 275-299
	G	55	2	W1068	826	22		25-53-26	150-199, 275-299
	G	6	2	W1068	557	22		25-53-25	050-099
	G	6	2	W1068	584	22		25-53-25	050-099
	G	6	2	W1068	587	22		25-53-25	050-099
	G	7	2	W1068	518	22		25-53-25	150-199, 275-299
	G	7	2	W1068	545	22		25-53-23	050-099
	G	7	2	W1068	555	22		25-53-23	050-099
	G	7	2	W1068	572	22		25-53-23	050-099
	G	7	2	W1068	577	22		25-53-24	150-199, 275-299
	G	7	2	W1068	587	22		25-53-24	150-199, 275-299
	G	7	2	W1068	697	22		25-53-23	050-099
	Z	8	BJ	W1068	515	22		25-53-24	150-199, 275-299
	H	8	2	W1068	649	22		25-53-23	050-099
	H	8	2	W1068	659	22		25-53-23	050-099
	Z	8	BJ	W1068	682	22		25-53-24	150-199, 275-299
	H	8	2	W1068	697	22		25-53-23	050-099
	H	8	2	W1068	753	22		25-53-23	050-099
	H	8	2	W1068	759	22		25-53-23	050-099
	Z	8	BJ	W1068	792	22		25-53-24	150-199, 275-299
	Z	8	BJ	W1068	839	22		25-53-26	150-199, 275-299
	Z	9	BJ	W1068	573	22		25-53-24	150-199, 275-299
	Z	9	BJ	W1068	680	22		25-53-24	150-199, 275-299
	Z	9	BJ	W1068	799	22		25-53-24	150-199, 275-299
	Z	9	BJ	W1068	840	22		25-53-26	150-199, 275-299
	D	A037	2	W1068	609	22		25-53-23	050-099
	D	A038	2	W1068	629	22		25-53-23	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 80

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0118		<b>BACT44B1775U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>D</b>	<b>DIODEBLOCK-REF284T0688- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0118	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	Y	A052	BJ	W1068	504	22		25-53-23	050-099
	Y	A052	BJ	W1068	838	22		25-53-26	050-099
	Y	A052	BJ	W1068	845	22		25-53-23	050-099
	Y	A053	BJ	W1068	515	22		25-53-24	050-099
	Y	A053	BJ	W1068	839	22		25-53-26	050-099
	Y	A053	BJ	W1068	847	22		25-53-24	050-099
	Y	A054	BJ	W1068	194	22		25-53-26	050-099
	Y	A054	BJ	W1068	684	22		25-53-24	050-099
	Y	A054	BJ	W1068	848	22		25-53-24	050-099
	Y	A055	BJ	W1068	37G	22		25-53-26	050-099
	Y	A055	BJ	W1068	707	22		25-53-26	050-099
	Y	A055	BJ	W1068	836	22		25-53-26	050-099
	D	C037	2	W1068	540	22		25-53-23	050-099
	D	C037	2	W1068	739	22		25-53-23	050-099
	D	C038	2	W1068	548	22		25-53-23	050-099
	D	C038	2	W1068	749	22		25-53-23	050-099
	Y	C052	BJ	W1068	513	22		25-53-23	050-099
	Y	C052	BJ	W1068	688	22		25-53-23	050-099
	Y	C052	BJ	W1068	833	22		25-53-26	050-099
	Y	C053	BJ	W1068	514	22		25-53-24	050-099
	Y	C053	BJ	W1068	840	22		25-53-26	050-099
	Y	C053	BJ	W1068	846	22		25-53-24	050-099
TB0119		<b>284T0384-10</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>D</b>	<b>RESISTORBLOCK-REF284T0115-R34-</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>F</b>	<b>BACM15C1A</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>H</b>	<b>BACM15C2A</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>X</b>	<b>BACM15C3A</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>Y</b>	<b>BACM15C3B</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>Z</b>	<b>BACM15C3B</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
	H	1	2	W0119	229R	24		22-14-21	ALL
	H	1	2	W0119	235R	24		22-32-12	ALL
	H	1	2	W0119	243R	24		34-61-22	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 81

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	H	1	2	W1119	228R	24		34-22-29	ALL
	G	101	2	W0119	558R	24		34-45-14	050-099, 150-156, 162-166
	G	101	2	W0119	559R	24		34-45-14	050-099, 150-156, 162-166
	G	101	2	W1119	560R	24		34-45-14	050-099, 150-156, 162-166, 275-276
	G	102	2	W0119	558B	24		34-45-14	050-099, 150-156, 162-166
	G	102	2	W0119	559B	24		34-45-14	050-099, 150-156, 162-166
	G	102	2	W1119	560B	24		34-45-14	050-099, 150-156, 162-166, 275-276
	G	103	2	W0109	608	24		34-46-12	050-099, 151
	G	103	2	W0109	609	24		34-46-12	ALL
	G	103	2	W0109	709	22		34-46-12	ALL
	G	105	2	W0119	123	24		34-22-27	ALL
	G	105	2	W0119	196	24		31-31-19	ALL
	G	105	2	W1119	073	24		34-22-27	ALL
	H	106	2	W0109	203R	24		27-32-11	ALL
	H	106	2	W0109	206R	24		34-22-19	ALL
	H	106	2	W0109	208R	24		34-46-12	ALL
	H	106	2	W0109	209R	24		34-22-39	ALL
	H	108	2	W0109	203B	24		27-32-11	ALL
	H	108	2	W0109	206B	24		34-22-19	ALL
	H	108	2	W0109	208B	24		34-46-12	ALL
	H	108	2	W0109	209B	24		34-22-39	ALL
	G	110	2	W0109	004	22		34-22-16	ALL
	G	110	2	W0109	728	22		34-46-11	050-099, 151
	G	110	2	W0109	921	22		34-46-13	150, 152-199, 275-299
	G	110	2	W0119	612	22		34-22-36	ALL
	G	110	2	W1119	128	22		34-22-26	ALL
	G	116	2	W0109	617	22		34-46-11	ALL
	G	116	2	W0109	718	24		31-51-21	ALL
	G	116	2	W0109	719	22		34-46-11	050-099, 151
	G	116	2	W0109	953	22		34-46-13	150, 152-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 82

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	H	119	2	W0109	104	22		34-46-12	050-099, 151
	H	119	2	W0109	106	22		34-46-12	050-099, 151
	H	119	2	W0109	109	22		34-46-11	050-099, 151
	H	119	2	W0109	111	22		34-46-12	151
	H	119	2	W0109	720	22		34-46-11	050-099, 151
	H	119	2	W0109	741	22		34-46-11	050-099, 151
	H	119	2	W0109	904	22		34-46-11	050-099, 151
	H	119	2	W0109	905	22		34-46-11	050-099, 151
	G	12	2	W0119	259R	24		34-22-91	ALL
	G	12	2	W0119	263R	24		34-22-29	ALL
	G	12	2	W0119	283R	24		34-22-39	ALL
	G	12	2	W1119	224R	24		34-22-29	ALL
	G	125	2	W0119	073	22		34-22-26	ALL
	G	125	2	W0119	635	22		34-22-13	ALL
	G	125	2	W1119	036	22		34-22-13	ALL
	G	125	2	W1119	075	22		34-22-26	ALL
	G	13	2	W0119	259B	24		34-22-91	ALL
	G	13	2	W0119	263B	24		34-22-29	ALL
	G	13	2	W0119	283B	24		34-22-39	ALL
	G	13	2	W1119	224B	24		34-22-29	ALL
	H	130	2	W0119	001	22		22-11-22	ALL
	H	130	2	W0119	002	20		22-11-22	ALL
	H	130	2	W0119	005	22		22-11-22	ALL
	H	130	2	W0119	008	22		22-11-22	ALL
	H	130	2	W0119	014	22		22-11-22	ALL
	G	133	2	W0109	211R	24		34-46-12	ALL
	G	133	2	W0109	603R	24		34-46-12	ALL
	G	133	2	W1119	233R	24		34-22-29	ALL
	G	134	2	W0109	211B	24		34-46-12	ALL
	G	134	2	W0109	603B	24		34-46-12	ALL
	G	134	2	W1119	233B	24		34-22-29	ALL
	G	138	2	W0119	130	24		34-22-27	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 83

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	G	138	2	W0119	131	24		34-22-37	ALL
	G	138	2	W1119	104	24		34-22-27	ALL
	H	139	2	W0109	102	24		31-51-21	ALL
	H	139	2	W0109	108	22		34-46-11	050-099, 151
	H	139	2	W0109	110	24		34-22-16	ALL
	H	139	2	W0109	616	22		34-46-11	ALL
	H	139	2	W0109	911	22		34-46-13	150, 152-199, 275-299
	H	139	2	W0119	160	24		34-22-36	ALL
	H	139	2	W1119	107	24		34-22-26	ALL
	H	139	2	W1119	112	24		34-22-26	ALL
	G	142	2	W0119	095	24		22-13-21	ALL
	G	142	2	W0119	096	22		34-22-26	ALL
	G	142	2	W1119	094	22		34-22-26	ALL
	G	143	2	W0109	231R	24		22-15-11	ALL
	G	143	2	W0119	231R	24		22-15-11	ALL
	G	144	2	W0109	231B	24		22-15-11	ALL
	G	144	2	W0119	231B	24		22-15-11	ALL
	H	148	2	W0109	064	24		22-14-11	ALL
	H	148	2	W0109	082	24		22-14-11	ALL
	H	148	2	W0119	057	24		22-14-21	ALL
	H	148	2	W0119	068	24		22-14-21	ALL
	H	148	2	W0129	057	24		22-14-31	ALL
	G	153	2	W0119	233R	24		22-15-11	ALL
	G	153	2	W0129	233R	24		22-15-11	ALL
	G	154	2	W0119	233B	24		22-15-11	ALL
	G	154	2	W0129	233B	24		22-15-11	ALL
	H	156	2	W0109	207R	24		34-46-12	ALL
	H	156	2	W0119	510R	24		27-32-21	ALL
	H	156	2	W0119	512R	24		34-22-39	ALL
	H	156	2	W1119	231R	24		34-22-29	ALL
	H	158	2	W0109	207B	24		34-46-12	ALL
	H	158	2	W0119	510B	24		27-32-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 84

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	H	158	2	W0119	512B	24		34-22-39	ALL
	H	158	2	W1119	231B	24		34-22-29	ALL
	G	160	2	W0119	902	20		23-32-21	150, 152-156, 162-199
	G	160	2	W0119	904	22		23-32-21	150, 152-156, 162-199
	G	160	2	W0119	913	20		23-32-21	150, 152-156, 162-199
	H	164	#	W0119	688	24		SPARE	150-199
	Z	167	BJ	W0109	931	22		34-46-13	150, 152-199, 275-299
	Z	167	BJ	W0109	933	22		34-46-13	150, 152-199, 275-299
	Z	167	BJ	W0109	934	22		34-46-13	150, 152-199, 275-299
	Z	167	BJ	W0109	936	22		34-46-13	150, 152-199, 275-299
	Z	167	BJ	W0109	938	22		34-46-13	150, 152-199, 275-299
	Z	167	BJ	W0109	988	22		34-46-13	150, 152-199, 275-299
	Z	167	BJ	W0109	989	22		34-46-13	150, 152-199, 275-299
	G	17	2	W0109	705	24		34-46-12	ALL
	G	17	2	W0109	706	24		34-46-12	ALL
	G	17	2	W0109	707	24		34-46-12	ALL
	Z	176	%	W0119	542R	24		31-31-20	ALL
	Z	177	%	W0119	542B	24		31-31-20	ALL
	G	180	2	W0109	024	24		31-31-26	ALL
	G	180	2	W0109	025	22		34-46-12	ALL
	G	180	2	W0109	708	24		34-46-12	ALL
	G	19	2	W0109	712	24		34-46-12	ALL
	G	19	2	W0109	716	24		34-46-12	ALL
	G	19	2	W0109	717	24		34-46-12	ALL
	Z	193	BJ	W0109	969	22		34-46-13	150, 152-199, 275-299
	Z	193	BJ	W0109	970	22		34-46-13	150, 152-199, 275-299
	Z	193	BJ	W0109	971	22		34-46-13	150, 152-199, 275-299
	Z	193	BJ	W0109	972	22		34-46-13	150, 152-199, 275-299
	Z	193	BJ	W0109	973	22		34-46-13	150, 152-199, 275-299
	G	22	2	W0119	179	24		34-22-27	ALL
	G	22	2	W0119	190	24		34-22-37	ALL
	G	22	2	W1119	010	24		34-22-27	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 85

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	G	23	2	W0119	180	24		34-22-27	ALL
	G	23	2	W0119	192	24		34-22-37	ALL
	G	23	2	W1119	011	24		34-22-27	ALL
	H	24	2	W0119	181	24		34-22-27	ALL
	H	24	2	W0119	188	24		34-43-21	ALL
	H	24	2	W0119	193	24		34-22-37	ALL
	H	24	2	W0119	197	24		31-31-19	ALL
	H	24	2	W1119	009	24		34-22-27	ALL
	G	26	2	W0119	183	24		34-22-27	ALL
	G	26	2	W0119	191	24		34-22-37	ALL
	G	26	2	W1119	008	24		34-22-27	ALL
	G	27	2	W0119	010	22		22-11-22	ALL
	G	27	2	W0119	012	22		22-11-22	ALL
	G	27	2	W0119	013	22		22-11-22	ALL
	G	28	2	W0119	253R	24		34-22-91	050-099, 150-156, 162-166
	G	28	2	W0119	264R	24		34-22-29	ALL
	G	28	2	W0119	282R	24		34-22-39	ALL
	G	28	2	W1119	225R	24		34-22-29	ALL
	G	29	2	W0119	253B	24		34-22-91	050-099, 150-156, 162-166
	G	29	2	W0119	264B	24		34-22-29	ALL
	G	29	2	W0119	282B	24		34-22-39	ALL
	G	29	2	W1119	225B	24		34-22-29	ALL
	H	3	2	W0119	229B	24		22-14-21	ALL
	H	3	2	W0119	235B	24		22-32-12	ALL
	H	3	2	W0119	243B	24		34-61-22	ALL
	H	3	2	W1119	228B	24		34-22-29	ALL
	G	30	2	W0119	280R	24		34-22-28	ALL
	G	30	2	W0119	297R	24		34-22-92	ALL
	G	30	2	W0119	505R	24		34-22-38	ALL
	G	30	2	W1119	222R	24		34-22-28	ALL
	G	31	2	W0119	280B	24		34-22-28	ALL
	G	31	2	W0119	297B	24		34-22-92	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 86

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	G	31	2	W0119	505B	24		34-22-38	ALL
	G	31	2	W1119	222B	24		34-22-28	ALL
	H	32	2	W0119	003	22		22-11-22	ALL
	H	32	2	W0119	011	22		22-11-22	ALL
	H	32	2	W0119	052	22		22-14-21	ALL
	G	34	2	W0119	208R	24		22-12-21	ALL
	G	34	2	W0119	214R	24		22-12-21	ALL
	G	34	2	W0119	237R	24		22-22-21	ALL
	G	35	2	W0119	208B	24		22-12-21	ALL
	G	35	2	W0119	214B	24		22-12-21	ALL
	G	35	2	W0119	237B	24		22-22-21	ALL
	G	37	2	W0119	221R	24		22-13-21	ALL
	G	37	2	W0119	223R	24		22-13-21	ALL
	G	37	2	W0119	228R	24		34-61-24	ALL
	G	37	2	W0119	908R	24		34-53-21	275-299
	G	38	2	W0119	221B	24		22-13-21	ALL
	G	38	2	W0119	223B	24		22-13-21	ALL
	G	38	2	W0119	228B	24		34-61-24	ALL
	G	38	2	W0119	908B	24		34-53-21	275-299
	G	39	2	W0119	060	22		22-14-21	ALL
	G	39	2	W0119	069	22		22-14-11	ALL
	G	39	2	W0119	074	22		22-14-31	ALL
	G	39	2	W0119	075	22		22-14-31	ALL
	G	40	2	W0119	120	24		22-15-12	ALL
	G	40	2	W0119	125	24		22-15-12	ALL
	G	40	2	W0119	126	24		22-15-12	ALL
	G	41	2	W0119	216R	24		22-12-21	ALL
	G	41	2	W0119	218R	24		22-12-21	ALL
	G	41	2	W1119	237R	24		22-12-21	ALL
	G	42	2	W0119	216B	24		22-12-21	ALL
	G	42	2	W0119	218B	24		22-12-21	ALL
	G	42	2	W1119	237B	24		22-12-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 87

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	H	43	2	W0119	204R	20		22-11-21	ALL
	H	43	2	W0119	205R	22		22-11-21	ALL
	H	43	2	W0119	206R	22		22-11-21	ALL
	H	43	2	W0119	207R	22		22-11-21	ALL
	H	45	2	W0119	204B	20		22-11-21	ALL
	H	45	2	W0119	205B	22		22-11-21	ALL
	H	45	2	W0119	206B	22		22-11-21	ALL
	H	45	2	W0119	207B	22		22-11-21	ALL
	G	47	2	W0119	089	24		22-12-21	ALL
	G	47	2	W0119	090	24		22-12-21	ALL
	G	47	2	W0119	091	22		22-22-21	ALL
	H	49	2	W0109	073	24		22-14-11	ALL
	H	49	2	W0109	101	24		22-14-31	ALL
	H	49	2	W0119	050	24		22-14-21	ALL
	H	49	2	W0129	077	24		22-14-31	ALL
	G	5	2	W0119	250R	24		34-22-38	ALL
	G	5	2	W0119	255R	24		34-22-28	ALL
	G	5	2	W1119	242R	24		34-22-28	ALL
	H	51	2	W0109	068	24		22-14-11	ALL
	H	51	2	W0109	070	24		22-14-11	ALL
	H	51	2	W0119	046	24		22-14-21	ALL
	H	51	2	W0119	048	24		22-14-21	ALL
	H	51	2	W0129	080	24		22-14-31	ALL
	G	53	2	W0119	084	24		22-15-12	ALL
	G	53	2	W0119	085	24		22-15-12	ALL
	G	53	2	W0119	086	24		22-15-12	ALL
	G	54	2	W0119	281R	24		34-22-38	ALL
	G	54	2	W0119	298R	24		34-22-28	ALL
	G	54	2	W1119	220R	24		34-22-28	ALL
	G	55	2	W0119	281B	24		34-22-38	ALL
	G	55	2	W0119	298B	24		34-22-28	ALL
	G	55	2	W1119	220B	24		34-22-28	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 88

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	G	56	2	W0119	108	22		34-31-21	ALL
	G	56	2	W0119	110	24		34-33-21	ALL
	G	56	2	W0119	111	22		34-31-21	ALL
	H	57	2	W0109	071	24		22-14-11	ALL
	H	57	2	W0109	072	24		22-14-11	ALL
	H	57	2	W0119	049	24		22-14-21	ALL
	H	57	2	W0119	054	24		22-14-21	ALL
	H	57	2	W0129	079	24		22-14-31	ALL
	G	59	2	W0109	042	24		21-26-31	ALL
	G	59	2	W0109	618	24		21-26-31	ALL
	G	59	2	W0109	619	24		21-26-31	ALL
	G	6	2	W0119	250B	24		34-22-38	ALL
	G	6	2	W0119	255B	24		34-22-28	ALL
	G	6	2	W1119	242B	24		34-22-28	ALL
	G	60	2	W0109	123	22		21-51-11	ALL
	G	60	2	W0109	620	22		21-26-31	ALL
	G	60	2	W0109	621	22		21-51-11	ALL
	H	61	2	W0109	212R	24		34-61-14	ALL
	H	61	2	W0109	237R	24		34-43-11	ALL
	H	61	2	W0109	9015R	24		34-46-13	150, 152-199, 275-299
	H	61	2	W0119	285R	24		34-43-21	ALL
	H	61	2	W0119	286R	24		34-61-24	ALL
	H	61	2	W0119	296R	24		34-22-34	ALL
	H	61	2	W1119	201R	24		34-22-24	ALL
	H	61	2	W1119	240R	24		34-22-24	ALL
	H	63	2	W0109	212B	24		34-61-14	ALL
	H	63	2	W0109	237B	24		34-43-11	ALL
	H	63	2	W0109	9015B	24		34-46-13	150, 152-199, 275-299
	H	63	2	W0119	285B	24		34-43-21	ALL
	H	63	2	W0119	286B	24		34-61-24	ALL
	H	63	2	W0119	296B	24		34-22-34	ALL
	H	63	2	W1119	201B	24		34-22-24	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 89

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	H	63	2	W1119	240B	24		34-22-24	ALL
	H	65	2	W0119	215R	24		22-12-21	ALL
	H	65	2	W0119	240R	24		34-12-22	ALL
	H	65	2	W0119	241R	24		27-11-22	ALL
	H	67	2	W0119	215B	24		22-12-21	ALL
	H	67	2	W0119	240B	24		34-12-22	ALL
	H	67	2	W0119	241B	24		27-11-22	ALL
	G	69	2	W0119	170	24		27-48-11	ALL
	G	69	2	W0119	171	24		27-48-11	ALL
	G	69	2	W0119	172	24		27-48-11	ALL
	G	70	2	W0109	520	22		21-66-41	050-099, 150, 152-199
	G	70	2	W0109	521	22		21-66-31	050-099, 150, 152-199
	G	70	2	W0109	523	22		21-66-41	150, 152-199
	G	72	2	W0119	256R	24		34-31-21	ALL
	G	72	2	W0119	257R	24		34-31-21	ALL
	G	72	2	W0119	258R	24		34-31-21	ALL
	G	73	2	W0119	256B	24		34-31-21	ALL
	G	73	2	W0119	257B	24		34-31-21	ALL
	G	73	2	W0119	258B	24		34-31-21	ALL
	G	76	2	W0119	045	24		22-13-21	ALL
	G	76	2	W0119	107	22		34-31-21	ALL
	G	76	2	W0119	112	24		22-13-21	ALL
	G	79	2	W0109	027	18		21-61-51	150-199, 275-299
	G	79	2	W0109	028	24		21-61-51	150-199, 275-299
	G	82	2	W1119	001	24		34-22-24	ALL
	G	82	2	W1119	024	24		34-22-24	ALL
	G	82	2	W1119	029	24		34-22-24	ALL
	G	83	2	W1119	002	24		34-22-24	ALL
	G	83	2	W1119	025	24		34-22-24	ALL
	G	83	2	W1119	028	24		34-22-24	ALL
	G	84	2	W1119	003	24		34-22-24	ALL
	G	84	2	W1119	026	24		34-22-24	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 90

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	G	84	2	W1119	027	24		34-22-24	ALL
	G	85	2	W1119	005	24		34-22-25	ALL
	G	85	2	W1119	030	24		34-22-24	ALL
	G	85	2	W1119	033	24		34-22-25	ALL
	G	86	2	W1119	006	24		34-22-25	ALL
	G	86	2	W1119	031	24		34-22-24	ALL
	G	86	2	W1119	034	24		34-22-25	ALL
	G	89	2	W1119	007	24		34-22-25	ALL
	G	89	2	W1119	032	24		34-22-24	ALL
	G	89	2	W1119	035	24		34-22-25	ALL
	F	A007	2	W0109	9017R	24		34-22-29	150, 152-199, 275-299
	F	A007	2	W0119	287R	24		34-22-29	ALL
	F	A007	2	W1119	229R	24		34-22-29	050-099, 151
	Y	A008	BJ	W0119	252R	24		34-31-21	ALL
	Y	A008	BJ	W0119	289R	24		34-61-22	ALL
	Y	A008	BJ	W0119	543R	24		31-31-20	ALL
	Y	A008	BJ	W1119	227R	24		34-22-29	ALL
	Y	A009	BJ	W0109	9016R	24		34-46-13	150, 152-199, 275-299
	Y	A009	BJ	W0109	9017R	24		34-22-29	150, 152-199, 275-299
	Y	A009	BJ	W1119	229R	24		34-22-29	150, 152-199, 275-299
	D	A014	2	W0109	732	24		34-46-12	050-099, 150-199, 275-278
	D	A014	2	W0109	733	24		34-46-12	050-099, 150-199, 275-278
	D	A015	2	W0109	705	24		34-46-12	ALL
	D	A016	2	W0109	733	24		34-46-12	050-099, 150-199, 275-278
	D	A018	2	W0109	731	24		34-46-12	050-099, 151
	D	A018	2	W0109	732	24		34-46-12	050-099, 150-199, 275-278
	F	A020	2	W0109	202R	24		34-22-28	ALL
	F	A020	2	W1119	241R	24		34-22-28	ALL
	F	A021	2	W0119	109	22		34-31-21	ALL
	F	A021	2	W1119	016	22		34-31-21	ALL
	D	A036	2	W0119	199	24		31-31-19	ALL
	F	A071	2	W0119	189	24		34-22-26	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 91

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	F	A071	2	W1119	012	24		34-22-26	ALL
	Y	A077	BJ	W0109	213R	24		21-61-51	ALL
	Y	A077	BJ	W0109	214R	24		21-61-51	ALL
	Y	A077	BJ	W0109	215R	24		21-61-51	ALL
	Y	A081	BJ	W0119	284R	24		34-22-38	ALL
	Y	A081	BJ	W0119	550R	24		34-61-26	ALL
	Y	A081	BJ	W1119	223R	24		34-22-28	ALL
	Y	A087	BJ	W0109	229R	24		21-61-81	050-099, 151-199, 275-299
	Y	A087	BJ	W0109	256R	22		21-61-81	050-099, 151-199, 275-299
	Y	A087	BJ	W0109	257R	22		21-61-81	050-099, 151-199, 275-299
	D	A090	2	W0109	614	22		34-45-12	275-276
	Y	A091	BJ	W0109	908W	24		34-46-13	150, 152-199, 275-299
	Y	A091	BJ	W0109	909W	24		34-46-13	150, 152-199, 275-299
	Y	A091	BJ	W0109	910W	24		34-46-13	150, 152-199, 275-299
	Y	A092	BJ	W0109	908WB	24		34-46-13	150, 152-199, 275-299
	Y	A092	BJ	W0109	909WB	24		34-46-13	150, 152-199, 275-299
	Y	A092	BJ	W0109	910WB	24		34-46-13	150, 152-199, 275-299
	D	A094	2	W0109	612	22		34-45-12	050-099, 150-152, 155-199, 275-299
	D	A094	2	W0109	613	22		34-45-12	050-099, 150-152, 155-156, 162-166, 275-276
	D	A095	2	W0109	613	22		34-45-12	050-099, 150-152, 155-156, 162-166, 275-276
	D	A095	2	W0109	614	22		34-45-12	050-099, 150-152, 155-156, 162-166, 275-276
	D	A095	2	W0109	622	22		34-45-12	157, 167-199, 277-299
	Y	A096	BJ	W0109	079	24		21-51-11	150-154, 275-276
	Y	A096	BJ	W0109	081	24		21-51-11	150-154, 275-276
	Y	A096	BJ	W0109	151	24		21-51-11	150-154, 275-276
	Y	A096	BJ	W0109	157	24		21-51-11	150-154, 275-276
	D	A097	2	W0109	614	22		34-45-12	050-099, 150-152, 155-156, 162-166

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 92

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	D	A097	2	W0109	623	22		34-45-12	157, 167-199, 277-299
	Y	A101	BJ	W0119	558R	24		34-45-14	157, 167-199, 277-299
	Y	A101	BJ	W0119	559R	24		34-45-14	157, 167-199, 277-299
	Y	A101	BJ	W1119	560R	24		34-45-14	157, 167-199, 277-299
	Y	A102	BJ	W0119	697	22		34-45-14	157, 167-199, 277-299
	Y	A102	BJ	W1119	043	22		34-45-14	157, 167-199, 277-299
	D	A104	2	W0119	198	24		31-31-19	ALL
	F	A111	2	W0119	072	22		34-22-26	ALL
	F	A111	2	W1119	074	22		34-22-26	ALL
	D	A113	2	W0109	612	22		34-45-12	153-154
	D	A114	2	W0109	622	22		34-45-12	153-154
	D	A115	2	W0109	623	22		34-45-12	153-154
	F	A117	2	W0119	613	22		34-22-26	ALL
	F	A117	2	W1119	601	22		34-22-26	ALL
	F	A118	2	W0109	236R	24		22-12-11	ALL
	F	A118	2	W1119	236R	24		22-12-11	ALL
	Y	A122	BJ	W0109	079	24		21-51-11	050-099, 155-199, 277-299
	Y	A122	BJ	W0109	081	24		21-51-11	050-099, 155-199, 277-299
	Y	A122	BJ	W0109	151	24		21-51-11	050-099, 155-199, 277-299
	Y	A122	BJ	W0109	157	24		21-51-11	050-099, 155-199, 277-299
	F	A123	2	W0109	083	24		22-15-12	ALL
	F	A123	2	W0119	083	24		22-15-12	ALL
	F	A126	2	W0109	056	22		22-14-21	ALL
	F	A126	2	W0119	056	22		22-14-21	ALL
	F	A127	2	W0119	064	24		22-14-21	ALL
	F	A127	2	W0129	062	24		22-14-21	ALL
	F	A128	2	W0109	093	24		22-41-11	ALL
	F	A128	2	W0119	093	24		22-41-11	ALL
	F	A129	2	W0109	239R	24		22-41-12	ALL
	F	A129	2	W0119	239R	24		22-41-12	ALL
	F	A136	2	W0119	509R	24		34-22-29	ALL
	F	A136	2	W1119	232R	24		34-22-29	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 93

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	F	A146	2	W0129	234R	24		22-12-31	ALL
	F	A146	2	W1119	234R	24		22-12-31	ALL
	F	A150	2	W0119	087	24		22-15-12	ALL
	F	A150	2	W0129	087	24		22-15-12	ALL
	F	A155	2	W0119	009	20		22-11-22	ALL
	F	A155	2	W0129	009	22		22-11-22	ALL
	X	A161	BJ	W0109	907	22		34-46-13	150, 152-199, 275-299
	X	A161	BJ	W0109	988	22		34-46-13	150, 152-199, 275-299
	X	A162	BJ	W0109	930	22		34-46-13	150, 152-199, 275-299
	X	A162	BJ	W0109	931	22		34-46-13	150, 152-199, 275-299
	X	A163	BJ	W0109	939	22		34-46-13	150, 152-199, 275-299
	X	A163	BJ	W0109	989	22		34-46-13	150, 152-199, 275-299
	X	A164	BJ	W0109	954	22		34-46-13	150, 152-199, 275-299
	X	A164	BJ	W0109	955	22		34-46-13	150, 152-199, 275-299
	X	A165	BJ	W0109	959	22		34-46-13	150, 152-199, 275-299
	X	A166	BJ	W0109	963	22		34-46-13	150, 152-199, 275-299
	D	A169	2	W0109	924	22		34-46-13	150, 152-199, 275-299
	F	A170	2	W0129	221R	24		34-22-28	ALL
	F	A170	2	W1119	221R	24		34-22-28	ALL
	Y	A171	BJ	W0109	909	22		34-46-13	150, 152-199, 275-299
	Y	A171	BJ	W0109	910	22		34-46-13	150, 152-199, 275-299
	Y	A171	BJ	W0109	913	22		34-46-13	150, 152-199, 275-299
	Y	A172	BJ	W0109	919	22		34-46-13	150, 152-199, 275-299
	Y	A172	BJ	W0109	920	22		34-46-13	150, 152-199, 275-299
	Y	A173	BJ	W0109	927	22		34-46-13	150, 152-199, 275-299
	Y	A173	BJ	W0109	929	22		34-46-13	150, 152-199, 275-299
	Y	A174	BJ	W0109	940	22		34-46-13	150, 152-199, 275-299
	Y	A174	BJ	W0109	949	22		34-46-13	150, 152-199, 275-299
	Y	A174	BJ	W0109	950	22		34-46-13	150, 152-199, 275-299
	D	A175	2	W0109	911	22		34-46-13	150, 152-199, 275-299
	D	A178	2	W0109	916	22		34-46-13	150, 152-199, 275-299
	D	A179	2	W0109	921	22		34-46-13	150, 152-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 94

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	D	A181	2	W0109	947	22		34-46-13	150, 152-199, 275-299
	D	A182	2	W0109	953	22		34-46-13	150, 152-199, 275-299
	Y	A183	BJ	W0109	074	24		21-28-11	ALL
	Y	A183	BJ	W0109	075	24		21-51-11	ALL
	Y	A183	BJ	W0109	076	24		21-28-11	ALL
	Y	A185	BJ	W0109	143	24		21-51-11	ALL
	Y	A185	BJ	W0109	152	24		21-61-81	ALL
	Y	A186	BJ	W0109	089	24		21-51-11	050, 150-154, 275-276
	Y	A186	BJ	W0109	148	24		21-51-11	050, 150-154, 275-276
	Y	A189	BJ	W0109	124	22		21-51-11	ALL
	Y	A189	BJ	W0109	125	22		21-51-11	ALL
	Y	A189	BJ	W0109	126	22		21-51-11	ALL
	Y	A189	BJ	W0109	621	22		21-51-11	ALL
	Y	A191	BJ	W0109	901W	24		34-46-13	150, 152-199, 275-299
	Y	A191	BJ	W0109	902W	24		34-46-13	150, 152-199, 275-299
	Y	A191	BJ	W0109	903W	24		34-46-13	150, 152-199, 275-299
	Y	A192	BJ	W0109	901WB	24		34-46-13	150, 152-199, 275-299
	Y	A192	BJ	W0109	902WB	24		34-46-13	150, 152-199, 275-299
	Y	A192	BJ	W0109	903WB	24		34-46-13	150, 152-199, 275-299
	D	A196	2	W0109	151	24		21-51-11	ALL
	D	A197	2	W0109	185	24		21-51-11	ALL
	X	B161	BJ	W0109	908	22		34-46-13	150, 152-199, 275-299
	X	B162	BJ	W0109	932	22		34-46-13	150, 152-199, 275-299
	X	B162	BJ	W0109	933	22		34-46-13	150, 152-199, 275-299
	X	B163	BJ	W0109	941	22		34-46-13	150, 152-199, 275-299
	X	B163	BJ	W0109	942	22		34-46-13	150, 152-199, 275-299
	X	B164	BJ	W0109	940	22		34-46-13	150, 152-199, 275-299
	X	B164	BJ	W0109	956	22		34-46-13	150, 152-199, 275-299
	X	B165	BJ	W0109	960	22		34-46-13	150, 152-199, 275-299
	F	C007	2	W0109	9017B	24		34-22-29	150, 152-199, 275-299
	F	C007	2	W0119	287B	24		34-22-29	ALL
	F	C007	2	W1119	229B	24		34-22-29	050-099, 151

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 95

Sep 04/2008



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	Y	C008	BJ	W0119	252B	24		34-31-21	ALL
	Y	C008	BJ	W0119	289B	24		34-61-22	ALL
	Y	C008	BJ	W0119	543B	24		31-31-20	ALL
	Y	C008	BJ	W1119	227B	24		34-22-29	ALL
	Y	C009	BJ	W0109	9016B	24		34-46-13	150, 152-199, 275-299
	Y	C009	BJ	W0109	9017B	24		34-22-29	150, 152-199, 275-299
	Y	C009	BJ	W1119	229B	24		34-22-29	150, 152-199, 275-299
	D	C014	2	W0129	101	24		34-46-12	050-099, 150-199, 275-278
	D	C015	2	W0109	730	24		34-46-12	ALL
	D	C016	2	W1119	101	24		34-46-12	050-099, 150-199, 275-278
	D	C018	2	W0109	715	24		34-46-12	050-099, 150-199, 275-278
	F	C020	2	W0109	202B	24		34-22-28	ALL
	F	C020	2	W1119	241B	24		34-22-28	ALL
	F	C021	2	W0109	015	22		34-22-23	ALL
	F	C021	2	W1119	017	22		34-22-23	ALL
	D	C036	2	W0119	197	24		31-31-19	ALL
	Y	C077	BJ	W0109	213B	24		21-61-51	ALL
	Y	C077	BJ	W0109	214B	24		21-61-51	ALL
	Y	C077	BJ	W0109	215B	24		21-61-51	ALL
	Y	C081	BJ	W0119	284B	24		34-22-38	ALL
	Y	C081	BJ	W0119	550B	24		34-61-26	ALL
	Y	C081	BJ	W1119	223B	24		34-22-28	ALL
	Y	C087	BJ	W0109	229B	24		21-61-81	050-099, 151-199, 275-299
	Y	C087	BJ	W0109	256B	22		21-61-81	050-099, 151-199, 275-299
	Y	C087	BJ	W0109	257B	22		21-61-81	050-099, 151-199, 275-299
	Y	C091	BJ	W0109	984	22		34-46-13	150, 152-199, 275-299
	Y	C091	BJ	W0109	985	22		34-46-13	150, 152-199, 275-299
	Y	C091	BJ	W0109	986	22		34-46-13	150, 152-199, 275-299
	D	C094	2	W0109	617	22		34-46-11	ALL
	D	C094	2	W0109	701	22		34-46-11	ALL
	D	C095	2	W0109	615	22		34-46-11	ALL
	D	C095	2	W0109	703	22		34-46-11	050-099, 151

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 96

Sep 04/2008



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	D	C095	2	W0109	947	22		34-46-13	150, 152, 155-199, 275-299
	Y	C096	BJ	W0109	116	24		21-51-11	150-154, 275-276
	Y	C096	BJ	W0109	164	24		21-61-81	150-154, 275-276
	Y	C096	BJ	W0109	185	24		21-51-11	150-154, 275-276
	D	C097	2	W0109	107	22		34-46-11	ALL
	D	C097	2	W0109	616	22		34-46-11	ALL
	Y	C101	BJ	W0119	558B	24		34-45-14	157, 167-199, 277-299
	Y	C101	BJ	W0119	559B	24		34-45-14	157, 167-199, 277-299
	Y	C101	BJ	W1119	560B	24		34-45-14	157, 167-199, 277-299
	D	C104	2	W0119	196	24		31-31-19	ALL
	F	C112	2	W0119	029	24		33-16-14	ALL
	F	C112	2	W1119	018	24		33-16-14	ALL
	D	C114	2	W0109	947	22		34-46-13	153-154
	F	C118	2	W0109	236B	24		22-12-11	ALL
	F	C118	2	W1119	236B	24		22-12-11	ALL
	Y	C122	BJ	W0109	116	24		21-51-11	050-099, 155-199, 277-299
	Y	C122	BJ	W0109	164	24		21-61-81	050-099, 155-199, 277-299
	Y	C122	BJ	W0109	185	24		21-51-11	050-099, 155-199, 277-299
	F	C126	2	W0119	055	24		22-14-21	ALL
	F	C126	2	W0129	089	24		22-14-21	ALL
	F	C127	2	W0119	077	24		22-15-12	ALL
	F	C127	2	W0129	006	24		22-15-12	ALL
	F	C128	2	W0109	065	24		22-15-12	ALL
	F	C128	2	W0119	094	24		22-15-12	ALL
	F	C129	2	W0109	239B	24		22-41-12	ALL
	F	C129	2	W0119	239B	24		22-41-12	ALL
	F	C136	2	W0119	509B	24		34-22-29	ALL
	F	C136	2	W1119	232B	24		34-22-29	ALL
	F	C146	2	W0129	234B	24		22-12-31	ALL
	F	C146	2	W1119	234B	24		22-12-31	ALL
	X	C161	BJ	W0109	912	22		34-46-13	150, 152-199, 275-299
	X	C161	BJ	W0109	913	22		34-46-13	150, 152-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 97

Sep 04/2008



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	X	C162	BJ	W0109	935	22		34-46-13	150, 152-199, 275-299
	X	C162	BJ	W0109	936	22		34-46-13	150, 152-199, 275-299
	X	C163	BJ	W0109	943	22		34-46-13	150, 152-199, 275-299
	X	C163	BJ	W0109	944	22		34-46-13	150, 152-199, 275-299
	X	C164	BJ	W0109	957	22		34-46-13	150, 152-199, 275-299
	X	C165	BJ	W0109	961	22		34-46-13	150, 152-199, 275-299
	D	C169	2	W0109	923	22		34-46-13	150, 152-199, 275-299
	F	C170	2	W0129	221B	24		34-22-28	ALL
	F	C170	2	W1119	221B	24		34-22-28	ALL
	Y	C171	BJ	W0109	914	22		34-46-13	150, 152-199, 275-299
	Y	C171	BJ	W0109	915	22		34-46-13	150, 152-199, 275-299
	Y	C172	BJ	W0109	922	22		34-46-13	150, 152-199, 275-299
	Y	C172	BJ	W0109	923	22		34-46-13	150, 152-199, 275-299
	Y	C173	BJ	W0109	942	22		34-46-13	150, 152-199, 275-299
	Y	C173	BJ	W0109	944	22		34-46-13	150, 152-199, 275-299
	Y	C173	BJ	W0109	945	22		34-46-13	150, 152-199, 275-299
	Y	C173	BJ	W0109	946	22		34-46-13	150, 152-199, 275-299
	Y	C174	BJ	W0109	951	22		34-46-13	150, 152-199, 275-299
	Y	C174	BJ	W0109	952	22		34-46-13	150, 152-199, 275-299
	Y	C174	BJ	W0109	955	22		34-46-13	150, 152-199, 275-299
	D	C175	2	W0109	910	22		34-46-13	150, 152-199, 275-299
	D	C178	2	W0109	915	22		34-46-13	150, 152-199, 275-299
	D	C179	2	W0109	920	22		34-46-13	150, 152-199, 275-299
	D	C181	2	W0109	946	22		34-46-13	150, 152-199, 275-299
	D	C182	2	W0109	952	22		34-46-13	150, 152-199, 275-299
	Y	C183	BJ	W0109	061	24		21-43-11	ALL
	Y	C183	BJ	W0109	155	24		21-43-11	ALL
	Y	C184	BJ	W0109	086	24		21-51-11	ALL
	Y	C184	BJ	W0109	097	24		21-51-11	ALL
	Y	C184	BJ	W0109	117	24		21-51-11	ALL
	Y	C185	BJ	W0109	144	24		21-51-11	ALL
	Y	C185	BJ	W0109	159	24		21-61-81	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 98

Sep 04/2008



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		284T0384-10 (continued)					SHELF/E01/05		ALL
TB0119	D	RESISTORBLOCK-REF284T0115-R34- (continued)					SHELF/E01/05		ALL
TB0119	F	BACM15C1A (continued)					SHELF/E01/05		ALL
TB0119	G	BACM15C1B (continued)					SHELF/E01/05		ALL
TB0119	H	BACM15C2A (continued)					SHELF/E01/05		ALL
TB0119	X	BACM15C3A (continued)					SHELF/E01/05		ALL
TB0119	Y	BACM15C3B (continued)					SHELF/E01/05		ALL
TB0119	Z	BACM15C3B (continued)					SHELF/E01/05		ALL
	Y	C186	BJ	W0109	085	24		21-51-11	ALL
	Y	C186	BJ	W0109	090	24		21-51-11	ALL
	Y	C186	BJ	W0109	149	24		21-51-11	ALL
	Y	C189	BJ	W0109	098	24		21-51-11	ALL
	Y	C189	BJ	W0109	118	24		21-51-11	ALL
	Y	C189	BJ	W0109	119	24		21-51-11	ALL
	Y	C191	BJ	W0109	966	22		34-46-13	150, 152-199, 275-299
	Y	C191	BJ	W0109	967	22		34-46-13	150, 152-199, 275-299
	Y	C191	BJ	W0109	968	22		34-46-13	150, 152-199, 275-299
	Y	C192	BJ	W0109	975	22		34-46-13	150, 152-199, 275-299
	Y	C192	BJ	W0109	976	22		34-46-13	150, 152-199, 275-299
	Y	C192	BJ	W0109	977	22		34-46-13	150, 152-199, 275-299
	D	C196	2	W0109	075	24		21-51-11	ALL
	D	C197	2	W0109	157	24		21-51-11	ALL
	Y	CAP	Y	W0109	084	24		21-51-11	050, 150-154, 275-276
	X	D161	BJ	W0109	928	22		34-46-13	150, 152-199, 275-299
	X	D161	BJ	W0109	929	22		34-46-13	150, 152-199, 275-299
	X	D162	BJ	W0109	937	22		34-46-13	150, 152-199, 275-299
	X	D162	BJ	W0109	938	22		34-46-13	150, 152-199, 275-299
	X	D163	BJ	W0109	948	22		34-46-13	150, 152-199, 275-299
	X	D163	BJ	W0109	949	22		34-46-13	150, 152-199, 275-299
	X	D164	BJ	W0109	958	22		34-46-13	150, 152-199, 275-299
	X	D165	BJ	W0109	962	22		34-46-13	150, 152-199, 275-299
	G	DED		W0109	028Z			21-61-51	150-199, 275-299
	G	DED		W0109	123Z			21-51-11	ALL
	G	DED		W0109	621Z			21-51-11	ALL
	Y	DED		W0109	621Z			21-51-11	ALL
	Y	DED		W0109	901Z			34-46-13	150, 152-199, 275-299
	Y	DED		W0109	902Z			34-46-13	150, 152-199, 275-299
	Y	DED		W0109	903Z			34-46-13	150, 152-199, 275-299
	Y	DED		W0109	908Z			34-46-13	150, 152-199, 275-299
	Y	DED		W0109	909Z			34-46-13	150, 152-199, 275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 99

Sep 04/2008





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0119		<b>284T0384-10 (continued)</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>D</b>	<b>RESISTORBLOCK-REF284T0115-R34- (continued)</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0119	<b>Z</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
	Y	DED		W0109	910Z			34-46-13	150, 152-199, 275-299
	H	DED		W0109	915Z			34-46-13	150, 152-199, 275-299
	Y	DED		W0109	916Z			34-46-13	150, 152-199, 275-299
	Y	DED		W0109	917Z			34-22-29	150, 152-199, 275-299
	H	DED		W0119	001Z			22-11-22	ALL
	H	DED		W0119	002Z			22-11-22	ALL
	H	DED		W0119	005Z			22-11-22	ALL
	H	DED		W0119	008Z			22-11-22	ALL
	H	DED		W0119	014Z			22-11-22	ALL
	F	DED		W0119	064Z			22-14-21	ALL
	F	DED		W0119	077Z			22-15-12	ALL
	F	DED		W0119	093Z			22-41-11	ALL
	F	DED		W0119	094Z			22-15-12	ALL
	G	DED		W0119	902Z			23-32-21	150, 152-156, 162-199
	F	DED		W1119	012Z			34-22-26	ALL
	F	DED		W1119	074Z			34-22-26	ALL
TB0120		<b>BACT44B1050U</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>D</b>	<b>DIODEBLOCK-REF284T0687-</b>					<b>P039-00/ /</b>		<b>050-099, 275-299</b>
TB0120	<b>G</b>	<b>BACM15C1B</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>H</b>	<b>BACM15C2A</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>Y</b>	<b>BACM15C3B</b>					<b>P039-00/ /</b>		<b>150-199, 275-299</b>
	H	1	2	W1068	092	22		25-53-26	ALL
	H	1	2	W1068	093	22		25-53-26	ALL
	H	1	2	W1068	094	22		25-53-26	ALL
	H	1	2	W1068	095	22		25-53-26	ALL
	H	1	2	W1068	096	22		25-53-27	050-099, 150-199
	H	1	2	W1068	39A	22		25-53-26	ALL
	G	13	2	W1068	114	22		25-53-26	ALL
	G	13	2	W1068	131	22		25-53-26	ALL
	G	13	2	W1068	132	22		25-53-26	ALL
	G	14	2	W1068	116	22		25-53-26	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 100

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0120		<b>BACT44B1050U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P039-00/ /</b>		<b>050-099, 275-299</b>
TB0120	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>150-199, 275-299</b>
	G	14	2	W1068	134	22		25-53-26	ALL
	G	14	2	W1068	135	22		25-53-26	ALL
	G	15	2	W1068	32A	20		25-53-21	150-199, 275-299
	G	15	2	W1068	590	20		25-53-21	ALL
	G	15	2	W1068	868	20		25-53-21	ALL
	G	15	2	W1068	869	20		25-53-21	ALL
	G	20	2	W1068	048	18		33-37-21	050-099
	G	20	2	W1068	048	16		33-37-21	150-199, 275-299
	G	20	2	W1068	065	18		33-37-21	050-099
	G	20	2	W1068	065	16		33-37-21	150-199, 275-299
	G	20	2	W1068	066	18		33-37-21	050-099
	G	20	2	W1068	066	16		33-37-21	150-199, 275-299
	H	3	2	W1068	096	22		25-53-27	050-099, 150-199
	H	3	2	W1068	097	22		25-53-27	050-099, 150-199
	H	3	2	W1068	098	22		25-53-27	050-099, 150-199
	H	3	2	W1068	099	22		25-53-27	050-099, 150-199
	H	3	2	W1068	100	22		25-53-27	050-099, 150-199
	H	5	2	W1068	177	22		25-53-27	150-199
	H	5	2	W1068	178	22		25-53-27	150-199
	H	5	2	W1068	532	22		25-53-23	050-099
	H	5	2	W1068	576	22		25-53-25	050-099
	H	5	2	W1068	578	22		25-53-26	050-099
	H	5	2	W1068	579	22		25-53-26	050-099
	H	5	2	W1068	586	22		25-53-25	050-099
	H	5	2	W1068	597	22		25-53-27	050-099
	H	5	2	W1068	598	22		25-53-27	050-099, 150-199
	H	7	2	W1068	071	22		25-53-25	ALL
	H	7	2	W1068	072	22		25-53-25	ALL
	H	7	2	W1068	073	22		25-53-25	ALL
	H	7	2	W1068	081	22		25-53-25	ALL
	H	7	2	W1068	082	22		25-53-25	ALL
	H	7	2	W1068	083	22		25-53-25	ALL
	H	7	2	W1068	38A	22		25-53-25	ALL
	D	A021	2	W1068	182	22		25-53-26	050-099
	D	A021	2	W1068	800	22		25-53-26	050-099
	D	A022	2	W1068	195	22		25-53-26	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 101

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0120		<b>BACT44B1050U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P039-00/ /</b>		<b>050-099, 275-299</b>
TB0120	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0120	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>150-199, 275-299</b>
	D	C021	2	W1068	195	22		25-53-26	050-099
	D	C021	2	W1068	755	22		25-53-26	050-099
	D	C022	2	W1068	192	22		25-53-26	050-099
	D	C022	2	W1068	196	22		25-53-26	050-099
TB0122		<b>BACT44B0510U</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0122	<b>D</b>	<b>DIODEBLOCK-REF284T0687-</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0122	<b>F</b>	<b>BACM15C1A</b>					<b>P039-00/ /</b>		<b>150-199, 275-299</b>
TB0122	<b>G</b>	<b>BACM15C1B</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0122	<b>H</b>	<b>BACM15C2A</b>					<b>P039-00/ /</b>		<b>ALL</b>
	H	1	2	W1068	503	20		25-53-21	050-099
	H	1	2	W1068	521	20		25-53-21	050-099
	H	1	2	W1068	537	20		33-37-21	050-099
	H	1	2	W1068	589	20		25-53-21	050-099
	H	1	2	W1068	593	20		25-53-21	050-099
	H	1	2	W1068	594	20		33-37-21	050-099
	H	3	2	W1068	37B	22		25-53-25	050-099
	H	3	2	W1068	37E	22		25-53-25	050-099
	H	3	2	W1068	37V	22		25-53-26	050-099
	H	3	2	W1068	501	22		25-53-21	050-099
	H	3	2	W1068	542	22		25-53-21	050-099
	H	3	2	W1068	877	22		25-53-21	050-099
	H	3	2	W1068	883	22		25-53-25	050-099
	H	3	2	W1068	884	22		25-53-25	050-099
	H	5	2	W1068	170	22		25-53-26	050-099
	H	5	2	W1068	37T	22		25-53-23	050-099
	H	5	2	W1068	530	22		25-53-23	050-099
	H	5	2	W1068	531	22		25-53-23	050-099
	H	5	2	W1068	532	22		25-53-23	050-099
	H	5	2	W1068	566	22		25-53-23	050-099
	G	7	2	W1068	523	24		52-35-12	050-099
	G	7	2	W1068	804	24		52-35-12	050-099
	G	7	2	W1068	814	24		52-35-12	050-099
	G	8	2	W1068	805	24		52-35-12	050-099
	G	8	2	W1068	816	24		52-35-12	050-099
	G	8	2	W1068	822	24		52-35-12	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 102

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0122		<b>BACT44B0510U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0122	<b>D</b>	<b>DIODEBLOCK-REF284T0687- (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0122	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P039-00/ /</b>		<b>150-199, 275-299</b>
TB0122	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0122	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	D	A	2	W1068	599	20		25-53-21	050-099
	D	A	2	W1068	619	22		25-53-23	050-099
	D	A	2	W1068	639	22		25-53-23	050-099
	D	A001	2	W1068	597	20		25-53-21	150-199, 275-299
	D	A002	2	W1068	619	22		25-53-23	150-199, 275-299
	D	A003	2	W1068	609	22		25-53-23	150-199, 275-299
	D	A004	2	W1068	639	22		25-53-23	150-199, 275-299
	D	A005	2	W1068	629	22		25-53-23	150-199, 275-299
	D	A006	2	W1068	659	22		25-53-23	150-199, 275-299
	D	A007	2	W1068	649	22		25-53-23	150-199, 275-299
	D	A008	2	W1068	33M	22		25-53-23	150-199, 275-299
	D	A009	2	W1068	33P	22		25-53-23	150-199, 275-299
	D	A010	2	W1068	807	24		52-35-12	150-199, 275-299
	D	A011	2	W1068	727	22		25-53-26	150-199, 275-299
	D	A011	2	W1068	800	22		25-53-26	150-199, 275-299
	D	A012	2	W1068	195	22		25-53-26	150-199, 275-299
	D	C	2	W1068	009	22		25-53-23	050-099
	D	C	2	W1068	010	22		25-53-23	050-099
	D	C	2	W1068	522	20		25-53-21	050-099
	D	C001	2	W1068	522	20		25-53-21	150-199, 275-299
	D	C002	2	W1068	33E	22		25-53-23	150-199, 275-299
	D	C002	2	W1068	33F	22		25-53-23	150-199, 275-299
	D	C003	2	W1068	33F	22		25-53-23	150-199, 275-299
	D	C004	2	W1068	33G	22		25-53-23	150-199, 275-299
	D	C004	2	W1068	33H	22		25-53-23	150-199, 275-299
	D	C005	2	W1068	33H	22		25-53-23	150-199, 275-299
	D	C006	2	W1068	33J	22		25-53-23	150-199, 275-299
	D	C006	2	W1068	33K	22		25-53-23	150-199, 275-299
	D	C007	2	W1068	33K	22		25-53-23	150-199, 275-299
	D	C008	2	W1068	33R	22		25-53-23	150-199, 275-299
	D	C009	2	W1068	33R	22		25-53-23	150-199, 275-299
	D	C009	2	W1068	40A	22		25-53-23	150-199, 275-299
	D	C010	2	W1068	527	24		52-35-12	150-199, 275-299
	D	C011	2	W1068	195	22		25-53-26	150-199, 275-299
	D	C011	2	W1068	755	22		25-53-26	150-199, 275-299
	D	C012	2	W1068	192	22		25-53-26	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 103

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0122		BACT44B0510U (continued)					P039-00/ /		ALL
TB0122	D	DIODEBLOCK-REF284T0687- (continued)					P039-00/ /		ALL
TB0122	F	BACM15C1A (continued)					P039-00/ /		150-199, 275-299
TB0122	G	BACM15C1B (continued)					P039-00/ /		ALL
TB0122	H	BACM15C2A (continued)					P039-00/ /		ALL
	D	C012	2	W1068	196	22		25-53-26	150-199, 275-299
TB0127		284T0384-9					SHELF/E01/04		ALL
TB0127	F	BACM15C1A					SHELF/E01/04		ALL
TB0127	G	BACM15C1B					SHELF/E01/04		ALL
TB0127	H	BACM15C2A					SHELF/E01/04		ALL
TB0127	X	BACM15C3A					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B					SHELF/E01/04		ALL
	G			W0117	907Z			23-32-21	150, 152-156, 162-199
	G			W0117	910Z			23-32-21	150, 152-156, 162-199
	G			W0117	918Z			23-32-21	150, 152-156, 162-199
	G	105	2	W0117	103	24		34-22-36	ALL
	G	105	2	W1127	107	24		34-22-36	ALL
	G	105	2	W1127	112	24		34-22-36	ALL
	G	107	2	W0107	206R	24		34-22-13	ALL
	G	107	2	W0117	206R	24		34-22-23	ALL
	G	107	2	W1127	269R	24		34-22-33	ALL
	G	108	2	W0107	206B	24		34-22-13	ALL
	G	108	2	W0117	206B	24		34-22-23	ALL
	G	108	2	W1127	269B	24		34-22-33	ALL
	G	111	2	W0107	208R	24		34-22-13	ALL
	G	111	2	W0117	205R	24		34-22-23	ALL
	G	111	2	W1127	268R	24		34-22-33	ALL
	G	112	2	W0107	208B	24		34-22-13	ALL
	G	112	2	W0117	205B	24		34-22-23	ALL
	G	112	2	W1127	268B	24		34-22-33	ALL
	G	131	2	W0107	215R	24		22-12-11	ALL
	G	131	2	W0107	219R	24		22-12-11	ALL
	G	131	2	W1127	260R	24		22-12-11	ALL
	G	132	2	W0107	215B	24		22-12-11	ALL
	G	132	2	W0107	219B	24		22-12-11	ALL
	G	132	2	W1127	260B	24		22-12-11	ALL
	G	140	2	W0107	213R	24		22-12-31	ALL
	G	140	2	W0127	213R	24		22-12-31	ALL
	G	141	2	W0107	213B	24		22-12-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 104

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	G	141	2	W0127	213B	24		22-12-31	ALL
	G	142	2	W0107	207R	24		34-22-13	ALL
	G	142	2	W0117	207R	24		34-22-23	ALL
	G	142	2	W0117	262R	24		31-31-12	ALL
	G	142	2	W1127	262R	24		31-31-12	ALL
	G	143	2	W0107	207B	24		34-22-13	ALL
	G	143	2	W0117	207B	24		34-22-23	ALL
	G	143	2	W0117	262B	24		31-31-12	ALL
	G	143	2	W1127	262B	24		31-31-12	ALL
	G	15	2	W0107	9001R	24		34-22-39	150, 152-199, 275-299
	G	15	2	W0127	283R	24		34-22-39	ALL
	G	15	2	W0127	540R	24		31-31-20	ALL
	G	15	2	W1127	243R	24		34-22-39	ALL
	Z	153	%	W0127	249R	24		31-31-20	ALL
	Z	154	%	W0127	249B	24		31-31-20	ALL
	G	158	2	W0117	110	24		34-31-31	ALL
	G	158	2	W0127	109	24		34-33-31	ALL
	G	158	2	W0127	110	24		34-31-31	ALL
	G	16	2	W0107	9001B	24		34-22-39	150, 152-199, 275-299
	G	16	2	W0127	283B	24		34-22-39	ALL
	G	16	2	W0127	540B	24		31-31-20	ALL
	G	16	2	W1127	243B	24		34-22-39	ALL
	G	161	2	W0117	201R	24		22-12-21	ALL
	G	161	2	W0117	261R	24		22-12-21	ALL
	G	161	2	W1127	261R	24		22-12-21	ALL
	G	162	2	W0117	201B	24		22-12-21	ALL
	G	162	2	W0117	261B	24		22-12-21	ALL
	G	162	2	W1127	261B	24		22-12-21	ALL
	G	18	2	W0127	225R	24		22-13-31	ALL
	G	18	2	W0127	281R	24		34-22-82	ALL
	G	18	2	W0127	282R	24		34-22-38	ALL
	G	18	2	W1127	241R	24		34-22-38	ALL
	G	19	2	W0127	225B	24		22-13-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 105

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	G	19	2	W0127	281B	24		34-22-82	ALL
	G	19	2	W0127	282B	24		34-22-38	ALL
	G	19	2	W1127	241B	24		34-22-38	ALL
	G	21	2	W0127	252R	24		34-31-31	ALL
	G	21	2	W0127	253R	24		34-24-11	ALL
	G	21	2	W0127	539R	24		31-31-20	ALL
	G	21	2	W1127	247R	24		34-22-39	ALL
	G	22	2	W0127	252B	24		34-31-31	ALL
	G	22	2	W0127	253B	24		34-24-11	ALL
	G	22	2	W0127	539B	24		31-31-20	ALL
	G	22	2	W1127	247B	24		34-22-39	ALL
	G	23	2	W0127	108	22		34-31-31	ALL
	G	23	2	W1127	033	22		34-31-31	ALL
	G	29	2	W0127	014	24		22-15-12	ALL
	G	29	2	W0127	021	24		22-15-12	ALL
	G	29	2	W0127	042	24		22-15-12	ALL
	H	30	2	W0127	001	22		22-11-32	ALL
	H	30	2	W0127	002	20		22-11-32	ALL
	H	30	2	W0127	003	22		22-11-32	ALL
	H	30	2	W0127	005	22		22-11-32	ALL
	H	30	2	W0127	011	22		22-11-32	ALL
	G	32	2	W0117	048	24		22-14-11	ALL
	G	32	2	W0117	053	24		22-14-21	ALL
	G	32	2	W0127	070	24		22-14-31	ALL
	G	34	2	W0127	010	22		22-11-32	ALL
	G	34	2	W0127	012	22		22-11-32	ALL
	G	34	2	W0127	013	22		22-11-32	ALL
	H	35	2	W0127	204B	20		22-11-31	ALL
	H	35	2	W0127	205B	22		22-11-31	ALL
	H	35	2	W0127	206B	22		22-11-31	ALL
	H	35	2	W0127	207B	22		22-11-31	ALL
	H	37	2	W0127	204R	20		22-11-31	ALL
	H	37	2	W0127	205R	22		22-11-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 106

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	H	37	2	W0127	206R	22		22-11-31	ALL
	H	37	2	W0127	207R	22		22-11-31	ALL
	G	39	2	W0107	060	24		22-11-12	ALL
	G	39	2	W0117	051	24		22-11-22	ALL
	G	39	2	W0127	023	24		22-11-32	ALL
	G	39	2	W0127	025	24		22-11-32	ALL
	G	40	2	W0117	047	24		22-14-11	ALL
	G	40	2	W0117	054	24		22-14-21	ALL
	G	40	2	W0127	068	24		22-14-31	ALL
	H	41	2	W0127	008	22		22-11-32	ALL
	H	41	2	W0127	009	20		22-11-32	ALL
	H	41	2	W0127	036	22		22-11-22	ALL
	H	41	2	W0127	050	22		22-14-21	ALL
	H	41	2	W0127	054	22		22-14-11	ALL
	H	41	2	W0127	058	22		22-11-12	ALL
	G	43	2	W0127	076	24		22-15-12	ALL
	G	43	2	W0127	077	24		22-15-12	ALL
	G	43	2	W0127	078	24		22-15-12	ALL
	G	44	2	W0127	117	24		22-13-31	ALL
	G	44	2	W0127	118	22		34-22-36	ALL
	G	44	2	W1127	094	22		34-22-36	ALL
	G	45	2	W0107	059	24		22-11-12	ALL
	G	45	2	W0117	050	24		22-11-22	ALL
	G	45	2	W0127	017	24		22-11-32	ALL
	G	45	2	W0127	024	24		22-11-32	ALL
	H	50	2	W0127	208R	24		22-12-31	ALL
	H	50	2	W0127	214R	24		22-12-31	ALL
	H	50	2	W0127	236R	24		22-22-11	ALL
	H	52	2	W0127	208B	24		22-12-31	ALL
	H	52	2	W0127	214B	24		22-12-31	ALL
	H	52	2	W0127	236B	24		22-22-11	ALL
	G	56	2	W0127	216R	24		22-12-31	ALL
	G	56	2	W0127	217R	24		22-12-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 107

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	G	56	2	W0127	218R	24		22-12-31	ALL
	G	56	2	W1127	254R	24		22-12-31	ALL
	G	57	2	W0127	216B	24		22-12-31	ALL
	G	57	2	W0127	217B	24		22-12-31	ALL
	G	57	2	W0127	218B	24		22-12-31	ALL
	G	57	2	W1127	254B	24		22-12-31	ALL
	H	58	2	W0107	051	24		22-14-11	ALL
	H	58	2	W0117	045	24		22-14-21	ALL
	H	58	2	W0127	049	24		22-14-21	ALL
	H	58	2	W0127	053	24		22-14-11	ALL
	H	58	2	W0127	064	24		22-14-31	ALL
	G	61	2	W0127	056	24		22-14-21	ALL
	G	61	2	W0127	057	24		22-14-11	ALL
	G	61	2	W0127	059	24		22-14-11	ALL
	G	61	2	W0127	061	24		22-14-31	ALL
	H	62	2	W0107	049	24		22-14-11	ALL
	H	62	2	W0117	046	24		22-14-21	ALL
	H	62	2	W0127	051	24		22-14-21	ALL
	H	62	2	W0127	052	24		22-14-11	ALL
	H	62	2	W0127	073	24		22-14-31	ALL
	G	75	2	W0127	048	24		22-13-31	ALL
	G	75	2	W0127	107	22		34-31-31	ALL
	G	75	2	W0127	112	24		22-13-31	ALL
	G	82	2	W0127	154	24		34-24-11	ALL
	G	82	2	W0127	156	24		34-24-11	ALL
	G	82	2	W0127	160	24		34-24-11	050-099, 150-199
	G	83	2	W0117	625	20		23-32-21	150, 152-156, 162-199
	G	83	2	W0117	916	20		23-32-21	150, 152-156, 162-199
	G	83	2	W0117	917	20		23-32-21	150, 152-156, 162-199
	G	84	2	W0117	907	20		23-32-21	150, 152-156, 162-199
	G	84	2	W0117	910	20		23-32-21	150, 152-156, 162-199
	G	84	2	W0117	918	20		23-32-21	150, 152-156, 162-199
	F	A007	2	W0107	604	22		34-22-36	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 108

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	F	A007	2	W1127	601	22		34-22-36	ALL
	X	A012	BJ	W0107	236R	24		34-45-14	157, 167-199, 277-299
	X	A012	BJ	W1127	279R	24		34-45-14	157, 167-199, 277-299
	F	A014	2	W0127	161	24		34-46-12	050-099, 150-199, 275-278
	F	A014	2	W1127	111	24		34-46-12	050-099, 150-199, 275-278
	F	A017	2	W0107	203R	24		34-22-38	ALL
	F	A017	2	W1127	263R	24		34-22-38	ALL
	F	A054	2	W0117	202R	24		34-22-38	ALL
	F	A054	2	W1127	264R	24		34-22-38	ALL
	F	A064	2	W0107	003	24		34-22-38	ALL
	F	A064	2	W1127	633	24		34-22-38	ALL
	X	A065	BJ	W0117	242R	24		34-22-38	ALL
	X	A065	BJ	W1127	270R	24		34-22-38	ALL
	X	A066	BJ	W0107	209R	24		34-22-38	ALL
	X	A066	BJ	W1127	272R	24		34-22-38	ALL
	F	A074	2	W0107	202R	24		23-51-13	ALL
	F	A074	2	W0127	251R	24		23-51-13	ALL
	F	A101	2	W0107	204R	24		34-22-39	ALL
	F	A101	2	W1127	258R	24		34-22-39	ALL
	F	A102	2	W0117	203R	24		34-22-39	ALL
	F	A102	2	W1127	259R	24		34-22-39	ALL
	F	A103	2	W0107	205R	24		34-22-39	ALL
	F	A103	2	W1127	265R	24		34-22-39	ALL
	F	A106	2	W0117	101	24		34-22-37	ALL
	F	A106	2	W1127	104	24		34-22-37	ALL
	F	A113	2	W0117	002	22		34-22-13	ALL
	F	A113	2	W1127	042	22		34-22-13	ALL
	F	A115	2	W0107	239R	24		34-22-38	ALL
	F	A115	2	W1127	239R	24		34-22-38	ALL
	F	A117	2	W0107	016	24		34-22-36	ALL
	F	A117	2	W1127	016	24		34-22-36	ALL
	Y	A119	BJ	W0107	019	24		34-22-38	ALL
	Y	A119	BJ	W1127	019	24		34-22-38	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 109

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	Y	A119	BJ	W1127	624	24		34-22-38	ALL
	Y	A120	BJ	W0107	025	24		34-22-37	ALL
	Y	A120	BJ	W1127	025	24		34-22-37	ALL
	F	A121	2	W0107	027	24		34-22-37	ALL
	F	A121	2	W1127	027	24		34-22-37	ALL
	F	A122	2	W0107	248R	24		34-22-39	ALL
	F	A122	2	W1127	248R	24		34-22-39	ALL
	F	A123	2	W0107	201R	24		34-22-35	ALL
	F	A123	2	W1127	201R	24		34-22-35	ALL
	F	A125	2	W0107	086	24		22-41-11	ALL
	F	A125	2	W0127	087	24		22-41-11	ALL
	F	A126	2	W0107	250R	24		34-22-39	ALL
	F	A126	2	W1127	250R	24		34-22-39	ALL
	F	A127	2	W0107	251R	24		34-22-39	ALL
	F	A127	2	W1127	251R	24		34-22-39	ALL
	F	A129	2	W0107	232R	24		34-45-14	050-099, 153-199, 277-299
	F	A129	2	W1127	278R	24		34-45-14	050-099, 153-199, 277-299
	F	A130	2	W0107	052	24		22-41-13	ALL
	F	A130	2	W0127	095	24		22-41-13	ALL
	F	A133	2	W0107	230R	24		22-15-11	ALL
	F	A133	2	W0127	230R	24		22-15-11	ALL
	F	A134	2	W0107	217R	24		22-12-31	ALL
	F	A134	2	W0127	219R	24		22-12-31	ALL
	F	A135	2	W0107	223R	24		22-13-11	ALL
	F	A135	2	W0127	223R	24		22-13-31	ALL
	F	A136	2	W0107	232R	24		34-45-14	150-152
	F	A136	2	W1127	278R	24		34-45-14	150-152
	F	A137	2	W0107	045	24		22-15-12	ALL
	F	A137	2	W0127	090	24		22-15-12	ALL
	F	A138	2	W0117	044	24		22-15-12	ALL
	F	A138	2	W0127	084	24		22-15-12	ALL
	F	A139	2	W0107	079	24		22-15-12	ALL
	F	A139	2	W0127	079	24		22-15-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 110

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	F	A145	2	W0117	220R	24		34-22-34	ALL
	F	A145	2	W1127	220R	24		34-22-34	ALL
	F	A146	2	W0117	081	24		22-15-12	ALL
	F	A146	2	W0127	081	24		22-15-12	ALL
	F	A147	2	W0117	240R	24		34-22-38	ALL
	F	A147	2	W1127	240R	24		34-22-38	ALL
	F	A148	2	W0117	029	24		34-22-37	ALL
	F	A148	2	W1127	029	24		34-22-37	ALL
	F	A149	2	W0117	031	24		34-22-37	ALL
	F	A149	2	W1127	031	24		34-22-37	ALL
	F	A151	2	W0117	244R	24		34-22-39	ALL
	F	A151	2	W1127	244R	24		34-22-39	ALL
	F	A152	2	W0117	245R	24		34-22-39	ALL
	F	A152	2	W1127	245R	24		34-22-39	ALL
	F	A155	2	W0117	024	24		34-22-37	ALL
	F	A155	2	W1127	024	24		34-22-37	ALL
	F	A156	2	W0107	210R	24		22-41-12	ALL
	F	A156	2	W0127	239R	24		22-41-12	ALL
	F	A159	2	W0117	232R	24		22-15-11	ALL
	F	A159	2	W0127	232R	24		22-15-11	ALL
	F	A163	2	W0117	080	22		22-14-31	ALL
	F	A163	2	W0127	069	22		22-14-31	ALL
	Y	A181	BJ	W0117	234R	24		23-32-21	ALL
	Y	A181	BJ	W1127	255R	24		34-22-38	ALL
	Y	A181	BJ	W1127	274R	24		34-22-38	ALL
	Y	A182	BJ	W0117	204R	24		34-22-39	ALL
	Y	A182	BJ	W0117	247R	24		23-32-21	050-099, 151, 275-299
	Y	A182	BJ	W0117	247R	22		23-32-21	150, 152-199
	Y	A182	BJ	W1127	266R	24		34-22-39	ALL
	X	B012	BJ	W0107	236B	24		34-45-14	157, 167-199, 277-299
	X	B012	BJ	W1127	279B	24		34-45-14	157, 167-199, 277-299
	X	B065	BJ	W0117	242B	24		34-22-38	ALL
	X	B065	BJ	W1127	270B	24		34-22-38	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 111

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	X	B066	BJ	W0107	209B	24		34-22-38	ALL
	X	B066	BJ	W1127	272B	24		34-22-38	ALL
	X	C012	BJ	W0107	062	22		34-45-14	157, 167-199, 277-299
	X	C012	BJ	W1127	067	22		34-45-14	157, 167-199, 277-299
	F	C017	2	W0107	203B	24		34-22-38	ALL
	F	C017	2	W1127	263B	24		34-22-38	ALL
	F	C054	2	W0117	202B	24		34-22-38	ALL
	F	C054	2	W1127	264B	24		34-22-38	ALL
	X	C065	BJ	W0117	210R	24		34-22-38	ALL
	X	C065	BJ	W1127	271R	24		34-22-38	ALL
	X	C066	BJ	W0107	255R	24		34-22-38	ALL
	X	C066	BJ	W1127	273R	24		34-22-38	ALL
	F	C074	2	W0107	202B	24		23-51-13	ALL
	F	C074	2	W0127	251B	24		23-51-13	ALL
	F	C101	2	W0107	204B	24		34-22-39	ALL
	F	C101	2	W1127	258B	24		34-22-39	ALL
	F	C102	2	W0117	203B	24		34-22-39	ALL
	F	C102	2	W1127	259B	24		34-22-39	ALL
	F	C103	2	W0107	205B	24		34-22-39	ALL
	F	C103	2	W1127	265B	24		34-22-39	ALL
	F	C106	2	W0127	162	24		34-22-37	ALL
	F	C106	2	W1127	106	24		34-22-37	ALL
	F	C113	2	W0117	005	22		34-22-36	ALL
	F	C113	2	W1127	128	22		34-22-36	ALL
	F	C115	2	W0107	239B	24		34-22-38	ALL
	F	C115	2	W1127	239B	24		34-22-38	ALL
	Y	C120	BJ	W0107	026	24		34-22-37	ALL
	Y	C120	BJ	W1127	026	24		34-22-37	ALL
	F	C121	2	W0107	028	24		34-22-37	ALL
	F	C121	#	W0107	107	24		SPARE	150-199
	F	C121	2	W1127	028	24		34-22-37	ALL
	F	C122	2	W0107	248B	24		34-22-39	ALL
	F	C122	2	W1127	248B	24		34-22-39	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 112

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	F	C123	2	W0107	201B	24		34-22-35	ALL
	F	C123	2	W1127	201B	24		34-22-35	ALL
	F	C125	2	W0127	033	24		33-16-14	ALL
	F	C125	2	W1127	034	24		33-16-14	ALL
	F	C126	2	W0107	250B	24		34-22-39	ALL
	F	C126	2	W1127	250B	24		34-22-39	ALL
	F	C127	2	W0107	251B	24		34-22-39	ALL
	F	C127	2	W1127	251B	24		34-22-39	ALL
	F	C129	2	W0107	232B	24		34-45-14	050-099, 153-199, 277-299
	F	C129	2	W1127	278B	24		34-45-14	050-099, 153-199, 277-299
	F	C133	2	W0107	230B	24		22-15-11	ALL
	F	C133	2	W0127	230B	24		22-15-11	ALL
	F	C134	2	W0107	217B	24		22-12-31	ALL
	F	C134	2	W0127	219B	24		22-12-31	ALL
	F	C135	2	W0107	223B	24		22-13-11	ALL
	F	C135	2	W0127	223B	24		22-13-31	ALL
	F	C136	2	W0107	232B	24		34-45-14	150-152
	F	C136	2	W1127	278B	24		34-45-14	150-152
	F	C137	2	W0107	046	22		22-14-31	ALL
	F	C137	2	W0127	062	22		22-14-31	ALL
	F	C138	2	W0107	053	24		22-14-31	ALL
	F	C138	2	W0127	067	24		22-14-31	ALL
	F	C145	2	W0117	220B	24		34-22-34	ALL
	F	C145	2	W1127	220B	24		34-22-34	ALL
	F	C146	2	W0117	052	24		22-41-13	ALL
	F	C146	2	W0127	096	24		22-41-13	ALL
	F	C147	2	W0117	240B	24		34-22-38	ALL
	F	C147	2	W1127	240B	24		34-22-38	ALL
	F	C148	2	W0117	030	24		34-22-37	ALL
	F	C148	2	W1127	030	24		34-22-37	ALL
	F	C149	2	W0117	032	24		34-22-37	ALL
	F	C149	2	W1127	032	24		34-22-37	ALL
	F	C151	2	W0117	244B	24		34-22-39	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 113

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	F	C151	2	W1127	244B	24		34-22-39	ALL
	F	C152	2	W0117	245B	24		34-22-39	ALL
	F	C152	2	W1127	245B	24		34-22-39	ALL
	F	C156	2	W0107	210B	24		22-41-12	ALL
	F	C156	2	W0127	239B	24		22-41-12	ALL
	F	C159	2	W0117	232B	24		22-15-11	ALL
	F	C159	2	W0127	232B	24		22-15-11	ALL
	Y	C181	BJ	W0117	234B	24		23-32-21	ALL
	Y	C181	BJ	W1127	255B	24		34-22-38	ALL
	Y	C181	BJ	W1127	274B	24		34-22-38	ALL
	Y	C182	BJ	W0117	204B	24		34-22-39	ALL
	Y	C182	BJ	W0117	247B	24		23-32-21	050-099, 151, 275-299
	Y	C182	BJ	W0117	247B	22		23-32-21	150, 152-199
	Y	C182	BJ	W1127	266B	24		34-22-39	ALL
	X	D012	BJ	W0107	063	22		34-45-14	157, 167-199, 277-299
	X	D012	BJ	W1127	068	22		34-45-14	157, 167-199, 277-299
	X	D065	BJ	W0117	210B	24		34-22-38	ALL
	X	D065	BJ	W1127	271B	24		34-22-38	ALL
	X	D066	BJ	W0107	255B	24		34-22-38	ALL
	X	D066	BJ	W1127	273B	24		34-22-38	ALL
	F	DED		W0107	016Z			34-22-36	ALL
	H	DED		W0127	001Z			22-11-32	ALL
	H	DED		W0127	002Z			22-11-32	ALL
	H	DED		W0127	003Z			22-11-32	ALL
	H	DED		W0127	005Z			22-11-32	ALL
	H	DED		W0127	008Z			22-11-32	ALL
	H	DED		W0127	009Z			22-11-32	ALL
	H	DED		W0127	011Z			22-11-32	ALL
	H	DED		W0127	050Z			22-14-21	ALL
	H	DED		W0127	054Z			22-14-11	ALL
	F	DED		W0127	084Z			22-15-12	ALL
	F	DED		W0127	090Z			22-15-12	ALL
	Z	DED		W0127	249Z			31-31-20	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 114

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0127		284T0384-9 (continued)					SHELF/E01/04		ALL
TB0127	F	BACM15C1A (continued)					SHELF/E01/04		ALL
TB0127	G	BACM15C1B (continued)					SHELF/E01/04		ALL
TB0127	H	BACM15C2A (continued)					SHELF/E01/04		ALL
TB0127	X	BACM15C3A (continued)					SHELF/E01/04		ALL
TB0127	Y	BACM15C3B (continued)					SHELF/E01/04		ALL
TB0127	Z	BACM15C3B (continued)					SHELF/E01/04		ALL
	F	DED		W1127	016Z			34-22-36	ALL
	Y	DED		W1127	019Z			34-22-38	ALL
	F	DED		W1127	024Z			34-22-37	ALL
	Y	DED		W1127	025Z			34-22-37	ALL
	Y	DED		W1127	026Z			34-22-37	ALL
	F	DED		W1127	027Z			34-22-37	ALL
	F	DED		W1127	028Z			34-22-37	ALL
	F	DED		W1127	029Z			34-22-37	ALL
	F	DED		W1127	030Z			34-22-37	ALL
	F	DED		W1127	031Z			34-22-37	ALL
	F	DED		W1127	032Z			34-22-37	ALL
	G	DED		W1127	033Z			34-31-31	ALL
TB0130		284T0384					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64-					SHELF/E01/02		ALL
TB0130	F	BACM15C1A					SHELF/E01/02		ALL
TB0130	G	BACM15C1B					SHELF/E01/02		ALL
TB0130	H	BACM15C2A					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112-					SHELF/E01/02		ALL
TB0130	X	BACM15C3A					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B					SHELF/E01/02		ALL
	Y			W1103	298Z			34-45-14	153-154
	Y			W1103	500Z			34-45-14	153-154
	Y			W1103	FRB			34-45-14	153-154
	H	1	2	W1103	008	24		34-22-17	ALL
	H	1	2	W1103	031	24		34-22-17	ALL
	H	1	2	W1103	037	24		34-22-37	ALL
	H	1	2	W1103	151	24		34-61-25	ALL
	G	10	2	W1092	009	24		24-28-21	ALL
	G	10	2	W1092	134	24		24-28-21	ALL
	G	10	2	W1092	135	24		24-28-21	ALL
	G	109	2	W1103	230R	24		22-41-13	ALL
	G	109	2	W1103	231R	24		22-41-13	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 115

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	G	109	2	W1103	519R	24		22-41-13	ALL
	G	11	2	W1092	164	24		33-16-14	ALL
	G	11	2	W1103	018	24		33-16-14	ALL
	G	110	2	W1103	230B	24		22-41-13	ALL
	G	110	2	W1103	231B	24		22-41-13	ALL
	G	110	2	W1103	519B	24		22-41-13	ALL
	H	111	2	W1103	220R	24		34-22-18	ALL
	H	111	2	W1103	241R	24		34-46-11	ALL
	H	111	2	W1103	245R	24		34-22-18	ALL
	H	111	2	W1103	259R	24		34-22-38	ALL
	H	113	2	W1103	220B	24		34-22-18	ALL
	H	113	2	W1103	241B	24		34-46-11	ALL
	H	113	2	W1103	245B	24		34-22-18	ALL
	H	113	2	W1103	259B	24		34-22-38	ALL
	G	118	2	W1090	004	18		24-11-11	ALL
	G	118	2	W1092	098	22		24-11-11	ALL
	G	118	2	W1092	099	18		24-11-11	ALL
	G	12	2	W1103	224R	24		34-22-19	ALL
	G	12	2	W1103	247R	24		34-22-19	ALL
	G	12	2	W1103	257R	24		34-22-39	ALL
	G	12	2	W1103	263R	24		34-22-81	ALL
	H	121	2	W1103	229R	24		34-22-19	ALL
	H	121	2	W1103	249R	24		34-46-11	ALL
	H	121	2	W1103	265R	24		34-33-11	ALL
	H	121	2	W1103	273R	24		31-31-20	ALL
	H	121	2	W1103	294R	24		31-41-31	ALL
	H	123	2	W1103	229B	24		34-22-19	ALL
	H	123	2	W1103	249B	24		34-46-11	ALL
	H	123	2	W1103	265B	24		34-33-11	ALL
	H	123	2	W1103	273B	24		31-31-20	ALL
	H	123	2	W1103	294B	24		31-41-31	ALL
	G	128	2	W1103	105	24		34-22-16	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 116

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	G	128	2	W1103	112	24		34-22-16	ALL
	G	128	2	W1103	121	24		34-22-16	ALL
	G	129	2	W1103	074	22		34-22-16	ALL
	G	129	2	W1103	148	22		34-22-16	ALL
	G	129	2	W1103	149	24		34-22-38	ALL
	G	13	2	W1103	224B	24		34-22-19	ALL
	G	13	2	W1103	247B	24		34-22-19	ALL
	G	13	2	W1103	257B	24		34-22-39	ALL
	G	13	2	W1103	263B	24		34-22-81	ALL
	G	130	2	W1103	268R	24		34-22-13	ALL
	G	130	2	W1103	271R	24		31-31-12	ALL
	G	130	2	W1103	289R	24		31-31-12	ALL
	G	131	2	W1103	268B	24		34-22-13	ALL
	G	131	2	W1103	271B	24		31-31-12	ALL
	G	131	2	W1103	289B	24		31-31-12	ALL
	G	136	2	W1092	108	20		24-22-11	ALL
	G	136	2	W1092	113	24		24-22-11	ALL
	G	136	2	W1092	116	20		24-22-11	ALL
	G	137	2	W1092	792	24		32-61-14	050-099, 150-152, 155-199, 275-299
	G	137	2	W1100	125	24		32-61-14	050-099, 150-152, 155-199, 275-299
	G	137	2	W1103	603	22		34-45-13	050-099, 150-152, 155-199, 275-299
	G	14	2	W1103	001	24		34-22-14	ALL
	G	14	2	W1103	019	24		34-22-14	ALL
	G	14	2	W1103	030	24		34-22-14	ALL
	G	15	2	W1103	002	24		34-22-14	150-154, 275-276
	G	15	2	W1103	020	24		34-22-14	150-154, 275-276
	G	15	2	W1103	029	24		34-22-14	150-154, 275-276
	G	154	2	W1103	222R	24		34-22-18	ALL
	G	154	2	W1103	246R	24		34-22-18	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 117

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	G	154	2	W1103	261R	24		34-22-82	ALL
	G	155	2	W1103	222B	24		34-22-18	ALL
	G	155	2	W1103	246B	24		34-22-18	ALL
	G	155	2	W1103	261B	24		34-22-82	ALL
	G	16	2	W1103	003	24		34-22-14	150-154, 275-276
	G	16	2	W1103	021	24		34-22-14	150-154, 275-276
	G	16	2	W1103	028	24		34-22-14	150-154, 275-276
	G	161	2	W1096	201R	24		34-43-11	ALL
	G	161	2	W1100	217R	24		34-43-21	ALL
	G	161	2	W1103	254R	24		34-43-11	ALL
	G	162	2	W1096	201B	24		34-43-11	ALL
	G	162	2	W1100	217B	24		34-43-21	ALL
	G	162	2	W1103	254B	24		34-43-11	ALL
	G	17	2	W1103	005	24		34-22-15	150-152, 275-276
	G	17	2	W1103	022	24		34-22-14	150-152, 275-276
	G	17	2	W1103	025	24		34-22-15	150-152, 275-276
	G	170	2	W1090	001	24		29-11-32	ALL
	G	170	2	W1090	011	22		29-11-32	ALL
	G	170	2	W1092	054	24		29-11-32	ALL
	G	18	2	W1103	006	24		34-22-15	150-152, 275-276
	G	18	2	W1103	023	24		34-22-14	150-152, 275-276
	G	18	2	W1103	026	24		34-22-15	150-152, 275-276
	G	182	2	W1092	025	24		27-88-11	ALL
	G	182	2	W1092	129	24		31-31-13	ALL
	G	182	2	W1103	045	24		31-31-13	ALL
	G	19	2	W1103	007	24		34-22-15	ALL
	G	19	2	W1103	024	24		34-22-14	ALL
	G	19	2	W1103	027	24		34-22-15	ALL
	G	21	2	W1103	225R	24		34-22-19	ALL
	G	21	2	W1103	248R	24		34-22-19	ALL
	G	21	2	W1103	258R	24		34-22-39	ALL
	G	21	2	W1103	262R	24		34-22-81	050-099, 150-156, 162-166

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 118

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	G	22	2	W1103	225B	24		34-22-19	ALL
	G	22	2	W1103	248B	24		34-22-19	ALL
	G	22	2	W1103	258B	24		34-22-39	ALL
	G	22	2	W1103	262B	24		34-22-81	050-099, 150-156, 162-166
	H	23	2	W1098	900R	24		34-46-11	050-099, 150-166, 275-299
	H	23	2	W1100	216R	24		34-43-21	ALL
	H	23	2	W1103	201R	24		34-22-14	ALL
	H	23	2	W1103	250R	24		34-22-14	ALL
	H	23	2	W1103	255R	24		34-43-11	ALL
	H	23	2	W1103	256R	24		34-22-35	ALL
	H	23	2	W1103	264R	24		34-61-14	ALL
	H	23	2	W1103	274R	24		34-61-24	ALL
	H	23	2	W1103	297R	24		34-46-12	280-299
	H	25	2	W1098	900B	24		34-46-11	050-099, 150-166, 275-299
	H	25	2	W1100	216B	24		34-43-21	ALL
	H	25	2	W1103	201B	24		34-22-14	ALL
	H	25	2	W1103	250B	24		34-22-14	ALL
	H	25	2	W1103	255B	24		34-43-11	ALL
	H	25	2	W1103	256B	24		34-22-35	ALL
	H	25	2	W1103	264B	24		34-61-14	ALL
	H	25	2	W1103	274B	24		34-61-24	ALL
	H	25	2	W1103	297B	24		34-46-12	280-299
	G	29	2	W1103	010	24		34-22-17	ALL
	G	29	2	W1103	033	24		34-22-17	ALL
	G	29	2	W1103	035	24		34-22-37	ALL
	H	3	2	W1103	009	24		34-22-17	ALL
	H	3	2	W1103	032	24		34-22-17	ALL
	H	3	2	W1103	038	24		34-22-37	ALL
	H	3	2	W1103	039	24		34-43-11	ALL
	H	3	2	W1103	040	24		31-31-13	ALL
	G	30	2	W1103	011	24		34-22-17	ALL
	G	30	2	W1103	034	24		34-22-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 119

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	G	30	2	W1103	036	24		34-22-37	ALL
	G	32	2	W1092	568	24		32-09-11	ALL
	G	32	2	W1092	707	24		32-61-14	ALL
	G	32	2	W1092	710	24		32-61-14	ALL
	G	32	2	W1092	722	24		32-09-11	ALL
	G	33	2	W1092	069	24		24-27-11	ALL
	G	33	2	W1092	070	24		24-27-11	ALL
	G	33	2	W1092	545	24		24-27-11	ALL
	G	35	2	W1092	526	24		32-61-14	ALL
	G	35	2	W1092	559	24		32-61-14	ALL
	G	35	2	W1092	560	24		32-61-14	ALL
	G	37	2	W1092	063	24		32-61-14	ALL
	G	37	2	W1092	739	24		32-61-14	ALL
	G	37	2	W1100	119	24		32-61-14	ALL
	G	5	2	W1103	075	22		34-22-16	ALL
	G	5	2	W1103	099	22		34-22-23	ALL
	G	5	2	W1103	139	22		34-22-16	ALL
	G	52	2	W1092	757	24		32-71-11	150-199, 275-299
	G	52	2	W1092	764	24		32-71-11	150-199, 275-299
	G	52	2	W1092	765	24		32-71-11	150-199, 275-299
	G	59	2	W1092	016	24		21-31-11	ALL
	G	59	2	W1092	017	24		21-31-11	ALL
	G	59	2	W1092	020	24		21-31-11	ALL
	G	6	2	W1092	091	24		24-11-11	ALL
	G	6	2	W1092	648	24		24-11-11	ALL
	G	6	2	W1092	649	24		24-11-11	ALL
	G	7	2	W1092	597	24		30-41-11	ALL
	G	7	2	W1098	003	22		30-41-11	ALL
	G	7	2	W1098	021	22		30-41-11	ALL
	G	72	2	W1092	719	24		32-61-14	ALL
	G	72	2	W1092	720	24		32-61-14	ALL
	G	72	2	W1100	120	24		32-61-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 120

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	H	74	2	W1092	162	24		32-61-14	ALL
	H	74	2	W1092	515	24		32-61-14	ALL
	H	74	2	W1092	715	24		32-61-14	ALL
	H	74	2	W1092	716	24		32-61-14	ALL
	H	74	2	W1100	121	24		32-61-14	ALL
	G	76	2	W1092	056	24		32-61-14	ALL
	G	76	2	W1092	181	24		32-61-14	ALL
	G	76	2	W1092	519	24		32-61-14	ALL
	G	78	2	W1092	126	24		32-61-14	ALL
	G	78	2	W1092	141	24		32-61-14	ALL
	G	78	2	W1092	517	24		32-61-14	ALL
	G	8	2	W1092	596	24		30-41-11	ALL
	G	8	2	W1098	005	22		30-41-11	ALL
	G	8	2	W1098	022	22		30-41-11	ALL
	G	9	2	W1090	014	24		27-88-11	ALL
	G	9	2	W1092	002	24		27-88-11	ALL
	G	9	2	W1092	0AP	24		27-88-11	ALL
	G	91	2	W1092	538	20		24-22-12	ALL
	G	91	2	W1092	539	20		24-22-12	ALL
	G	91	2	W1092	540	24		24-22-12	ALL
	Y	A015	BJ	W1103	002	24		34-22-14	050-099, 155-199, 277-299
	Y	A015	BJ	W1103	020	24		34-22-14	050-099, 155-199, 277-299
	Y	A015	BJ	W1103	029	24		34-22-14	050-099, 155-199, 277-299
	Y	A016	BJ	W1103	005	24		34-22-15	050-099, 155-199, 277-299
	Y	A016	BJ	W1103	022	24		34-22-14	050-099, 155-199, 277-299
	Y	A016	BJ	W1103	025	24		34-22-15	050-099, 155-199, 277-299
	Y	A017	BJ	W1103	298R	24		34-45-14	ALL
	Y	A017	BJ	W1103	500R	24		34-45-14	050-099, 150-156, 162-166, 275-276
	Y	A017	BJ	W1103	522R	24		34-45-14	ALL
	Y	A018	BJ	W1103	005	24		34-22-15	153-154
	Y	A018	BJ	W1103	022	24		34-22-14	153-154

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 121

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	Y	A018	BJ	W1103	025	24		34-22-15	153-154
	F	A020	2	W1100	056	22		34-22-13	ALL
	F	A020	2	W1103	095	22		34-22-13	ALL
	F	A031	2	W1092	238R	24		27-32-21	ALL
	F	A031	2	W1100	204R	24		27-32-21	ALL
	F	A038	2	W1092	235R	24		32-61-11	ALL
	F	A038	2	W1100	203R	24		32-61-11	ALL
	F	A039	2	W1092	234R	24		32-61-11	ALL
	F	A039	2	W1100	202R	24		32-61-11	ALL
	F	A040	2	W1092	233R	24		32-61-11	ALL
	F	A040	2	W1100	201R	24		32-61-11	ALL
	Y	A042	BJ	W1100	232R	24		77-31-11	ALL
	Y	A042	BJ	W1100	280R	24		77-12-11	ALL
	Y	A043	BJ	W1092	620R	24		77-31-11	ALL
	Y	A043	BJ	W1092	682R	24		77-12-11	050-099, 162-199, 277-299
	Y	A043	BJ	W1100	279R	24		77-12-11	150-157, 275-276
	X	A044	BJ	W1096	208B	22		32-45-14	050-099, 150-199
	X	A044	BJ	W1100	282B	22		32-45-14	050-099, 150-199
	X	A045	BJ	W1096	208Z			32-45-14	050-099, 150-199
	X	A045	BJ	W1100	282Z			32-45-14	050-099, 150-199
	X	A046	BJ	W1096	210B	22		32-45-14	050-099, 150-199
	X	A046	BJ	W1100	284B	22		32-45-14	050-099, 150-199
	F	A048	2	W1092	174	24		78-36-11	ALL
	F	A048	2	W1100	501	24		78-36-11	ALL
	D	A049	2	W1092	763	24		32-71-11	150-199, 275-299
	X	A051	BJ	W1092	660B	24		77-35-11	ALL
	X	A051	BJ	W1103	267B	24		77-35-11	ALL
	D	A053	2	W1092	200	24		74-31-11	ALL
	D	A054	2	W1100	084	24		74-31-21	ALL
	D	A055	2	W1092	024	24		27-58-11	ALL
	F	A056	2	W1100	286R	24		36-23-21	156-162, 166-199, 277-299
	F	A057	2	W1092	723	24		32-61-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 122

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	F	A057	2	W1100	123	24		32-61-14	ALL
	F	A058	2	W1092	555	24		32-09-13	ALL
	F	A058	2	W1100	097	24		32-09-13	ALL
	F	A060	2	W1092	040	24		32-61-14	ALL
	F	A060	2	W1100	114	24		32-61-14	ALL
	F	A063	2	W1092	202Z			21-31-11	ALL
	F	A063	2	W1100	269Z			21-31-11	ALL
	F	A064	2	W1092	202R	24		21-31-11	ALL
	F	A064	2	W1100	269R	24		21-31-11	ALL
	F	A065	2	W1092	201Z			21-31-11	ALL
	F	A065	2	W1103	290Z			21-31-11	ALL
	F	A066	2	W1092	201B	24		21-31-11	ALL
	F	A066	2	W1103	290B	24		21-31-11	ALL
	F	A067	2	W1092	183	24		32-09-12	ALL
	F	A067	2	W1100	064	24		32-09-12	ALL
	F	A068	2	W1092	278R	24		78-36-21	ALL
	F	A068	2	W1100	226R	24		78-36-21	ALL
	F	A069	2	W1092	180	24		32-09-12	ALL
	F	A069	2	W1100	059	24		32-09-12	ALL
	F	A070	2	W1092	276R	24		78-36-21	ALL
	F	A070	2	W1100	224R	24		78-36-21	ALL
	F	A071	2	W1092	275R	24		78-36-21	ALL
	F	A071	2	W1100	223R	24		78-36-21	ALL
	F	A080	2	W1092	277R	24		78-36-21	ALL
	F	A080	2	W1100	225R	24		78-36-21	ALL
	F	A081	2	W1092	270B	24		78-34-21	ALL
	F	A081	2	W1100	222B	24		78-34-21	ALL
	F	A082	2	W1092	269B	24		78-34-21	ALL
	F	A082	2	W1100	221B	24		78-34-21	ALL
	F	A083	2	W1092	167	24		78-34-21	275-299
	F	A083	2	W1100	048	24		78-34-21	275-299
	D	A085	2	W1090	011	22		29-11-32	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 123

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	F	A086	2	W1092	167	24		78-34-21	050-099, 150-199
	F	A086	2	W1100	048	24		78-34-21	050-099, 150-199
	F	A087	2	W1092	133	24		31-31-13	ALL
	F	A087	2	W1103	049	24		31-31-13	ALL
	F	A088	2	W1092	131	24		31-31-13	ALL
	F	A088	2	W1103	047	24		31-31-13	ALL
	F	A090	2	W1092	127	24		31-31-13	ALL
	F	A090	2	W1103	043	24		31-31-13	ALL
	D	A092	2	W1092	022	24		21-31-11	ALL
	F	A095	2	W1092	206B	24		21-31-11	ALL
	F	A095	2	W1098	201B	24		21-31-11	ALL
	F	A096	2	W1092	262B	24		32-09-12	ALL
	F	A096	2	W1100	261B	24		32-09-12	ALL
	F	A097	2	W1092	206Z			21-31-11	ALL
	F	A097	2	W1098	201Z			21-31-11	ALL
	F	A102	2	W1100	274R	24		34-22-19	ALL
	F	A102	2	W1103	243R	24		34-22-19	ALL
	F	A103	2	W1092	670R	24		73-21-14	ALL
	F	A103	2	W1100	275R	24		73-21-14	ALL
	F	A104	2	W1092	670Z			73-21-14	ALL
	F	A104	2	W1100	275Z			73-21-14	ALL
	F	A105	2	W1092	627R	22		21-31-11	ALL
	F	A105	2	W1098	214R	20		21-31-11	ALL
	F	A115	2	W1100	273R	24		34-22-18	ALL
	F	A115	2	W1103	240R	24		34-22-18	ALL
	F	A117	2	W1090	003	20		24-11-11	ALL
	F	A117	2	W1092	102	22		24-11-11	ALL
	F	A127	2	W1092	752	24		31-31-21	ALL
	F	A127	2	W1103	054	24		31-31-21	ALL
	X	A132	BJ	W1100	281R	22		31-31-22	ALL
	X	A132	BJ	W1103	272R	22		31-31-22	050-099, 275-299
	X	A132	BJ	W1103	272R	24		31-31-22	150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 124

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	X	A133	BJ	W1100	281B	22		31-31-22	ALL
	X	A133	BJ	W1103	272B	22		31-31-22	050-099, 275-299
	X	A133	BJ	W1103	272B	24		31-31-22	150-199
	F	A135	2	W1092	087	24		33-24-11	ALL
	F	A135	2	W1100	022	24		33-24-11	ALL
	F	A138	2	W1092	252R	24		32-61-13	ALL
	F	A138	2	W1100	214R	24		32-61-13	ALL
	F	A139	2	W1092	251R	24		32-61-13	ALL
	F	A139	2	W1100	213R	24		32-61-13	ALL
	F	A140	2	W1092	250R	24		32-61-13	ALL
	F	A140	2	W1100	212R	24		32-61-13	ALL
	F	A141	2	W1092	570	24		32-09-21	ALL
	F	A141	2	W1100	104	24		32-09-21	ALL
	F	A142	2	W1096	101	24		34-22-17	ALL
	F	A142	2	W1103	104	24		34-22-17	ALL
	F	A143	2	W1090	016	24		31-51-41	ALL
	F	A143	2	W1092	595	24		31-51-41	ALL
	F	A144	2	W1096	207R	24		34-22-18	ALL
	F	A144	2	W1103	221R	24		34-22-18	ALL
	F	A149	2	W1100	055	22		22-41-11	ALL
	F	A149	2	W1103	063	22		22-41-11	ALL
	F	A150	2	W1100	227R	24		22-41-11	ALL
	F	A150	2	W1103	283R	24		22-41-11	ALL
	F	A151	2	W1100	228R	24		22-41-11	ALL
	F	A151	2	W1103	285R	24		22-41-11	ALL
	F	A153	2	W1100	260R	24		22-12-21	ALL
	F	A153	2	W1103	237R	24		22-12-21	ALL
	F	A158	2	W1096	203R	24		22-41-11	ALL
	F	A158	2	W1103	288R	24		22-41-11	ALL
	Y	A159	BJ	W1103	223R	24		34-61-16	ALL
	Y	A159	BJ	W1103	275R	24		34-22-38	ALL
	Y	A159	BJ	W1103	277R	24		34-61-16	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 125

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	F	A163	2	W1096	202R	24		22-12-31	ALL
	F	A163	2	W1103	234R	24		22-12-31	ALL
	F	A165	2	W1092	260R	24		32-61-13	ALL
	F	A165	2	W1100	211R	24		32-61-13	ALL
	D	A166	2	W1092	0AQ	24		27-81-21	ALL
	D	A166	2	W1092	0AS	24		27-81-21	ALL
	F	A167	2	W1092	258R	24		32-09-12	ALL
	F	A167	2	W1100	210R	24		32-09-12	ALL
	F	A168	2	W1092	257R	24		32-09-12	ALL
	F	A168	2	W1100	209R	24		32-09-12	ALL
	F	A169	2	W1092	153	24		32-42-11	ALL
	F	A169	2	W1100	107	24		32-42-11	ALL
	D	A171	2	W1092	01F	24		27-32-21	ALL
	D	A171	2	W1092	01G	24		27-32-21	ALL
	D	A172	2	W1092	563	22		78-34-11	ALL
	D	A173	2	W1092	564	24		78-34-11	ALL
	D	A174	2	W1100	049	22		78-34-21	ALL
	D	A175	2	W1100	050	24		78-34-21	ALL
	F	A176	2	W1092	248R	24		32-61-12	ALL
	F	A176	2	W1100	207R	24		32-61-12	ALL
	F	A177	2	W1092	247R	24		32-61-12	ALL
	F	A177	2	W1100	206R	24		32-61-12	ALL
	F	A178	2	W1092	246R	24		32-61-12	ALL
	F	A178	2	W1100	205R	24		32-61-12	ALL
	D	A179	2	W1092	743	24		32-61-14	ALL
	D	A180	2	W1092	745	24		32-61-14	ALL
	F	A181	2	W1092	073	24		32-61-14	ALL
	F	A181	2	W1100	113	24		32-61-14	ALL
	D	A183	2	W1092	066	24		32-61-14	ALL
	D	A184	2	W1092	738	24		32-61-14	ALL
	D	A185	2	W1092	705	24		32-61-14	ALL
	D	A185	2	W1092	706	24		32-61-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 126

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	D	A186	2	W1092	556	24		32-61-14	ALL
	D	A186	2	W1092	708	24		32-61-14	ALL
	D	A187	2	W1092	534	24		32-61-14	ALL
	D	A187	2	W1092	711	24		32-61-14	ALL
	D	A188	2	W1092	068	24		32-61-14	ALL
	D	A188	2	W1092	709	24		32-61-14	ALL
	R	A189	2	W1092	027	24		24-11-11	ALL
	D	A190	2	W1092	01B	24		27-32-11	ALL
	D	A190	2	W1092	01C	24		27-32-11	ALL
	D	A191	2	W1092	576	24		32-42-11	ALL
	D	A192	2	W1100	107	24		32-42-11	ALL
	D	A193	2	W1092	059	24		32-61-14	ALL
	D	A194	2	W1092	547	20		33-37-21	ALL
	D	A194	2	W1092	548	20		33-37-21	ALL
	D	A195	2	W1092	548	20		33-37-21	ALL
	D	A196	2	W1092	060	24		32-61-14	ALL
	D	A196	2	W1103	082	24		31-31-19	ALL
	D	A197	2	W1092	571	20		33-37-11	ALL
	X	B044	BJ	W1096	208R	22		32-45-14	050-099, 150-199
	X	B044	BJ	W1100	282R	22		32-45-14	050-099, 150-199
	X	B045	BJ	W1096	209Z			32-45-14	050-099, 150-199
	X	B045	BJ	W1100	283Z			32-45-14	050-099, 150-199
	X	B046	BJ	W1096	210R	22		32-45-14	050-099, 150-199
	X	B046	BJ	W1100	284R	22		32-45-14	050-099, 150-199
	X	B051	BJ	W1092	660R	24		77-35-11	ALL
	X	B051	BJ	W1103	267R	24		77-35-11	ALL
	X	B132	BJ	W1100	145	22		31-31-22	ALL
	X	B132	BJ	W1103	145	22		31-31-22	ALL
	Y	C015	BJ	W1103	003	24		34-22-14	050-099, 155-199, 277-299
	Y	C015	BJ	W1103	021	24		34-22-14	050-099, 155-199, 277-299
	Y	C015	BJ	W1103	028	24		34-22-14	050-099, 155-199, 277-299
	Y	C016	BJ	W1103	006	24		34-22-15	050-099, 155-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 127

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	Y	C016	BJ	W1103	023	24		34-22-14	050-099, 155-199, 277-299
	Y	C016	BJ	W1103	026	24		34-22-15	050-099, 155-199, 277-299
	Y	C017	BJ	W1103	298B	24		34-45-14	ALL
	Y	C017	BJ	W1103	500B	24		34-45-14	050-099, 150-156, 162-166, 275-276
	Y	C017	BJ	W1103	522B	24		34-45-14	ALL
	Y	C018	BJ	W1103	006	24		34-22-15	153-154
	Y	C018	BJ	W1103	023	24		34-22-14	153-154
	Y	C018	BJ	W1103	026	24		34-22-15	153-154
	F	C031	2	W1092	238B	24		27-32-21	ALL
	F	C031	2	W1100	204B	24		27-32-21	ALL
	F	C038	2	W1092	235B	24		32-61-11	ALL
	F	C038	2	W1100	203B	24		32-61-11	ALL
	F	C039	2	W1092	234B	24		32-61-11	ALL
	F	C039	2	W1100	202B	24		32-61-11	ALL
	F	C040	2	W1092	233B	24		32-61-11	ALL
	F	C040	2	W1100	201B	24		32-61-11	ALL
	F	C041	2	W1092	052	22		78-36-11	ALL
	F	C041	2	W1100	122	22		78-36-11	ALL
	Y	C042	BJ	W1100	232B	24		77-31-11	ALL
	Y	C042	BJ	W1100	280B	24		77-12-11	ALL
	Y	C043	BJ	W1092	620B	24		77-31-11	ALL
	Y	C043	BJ	W1092	682B	24		77-12-11	050-099, 162-199, 277-299
	Y	C043	BJ	W1100	279B	24		77-12-11	150-157, 275-276
	X	C044	BJ	W1096	209B	22		32-45-14	050-099, 150-199
	X	C044	BJ	W1100	283B	22		32-45-14	050-099, 150-199
	X	C045	BJ	W1096	210Z			32-45-14	050-099, 150-199
	X	C045	BJ	W1100	284Z			32-45-14	050-099, 150-199
	X	C046	BJ	W1096	211B	22		32-45-14	050-099, 150-199
	X	C046	BJ	W1100	285B	22		32-45-14	050-099, 150-199
	F	C048	2	W1092	172	24		78-36-11	ALL
	F	C048	2	W1100	502	24		78-36-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 128

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	D	C049	2	W1092	762	24		32-71-11	150-199, 275-299
	X	C051	BJ	W1092	659B	24		77-35-11	ALL
	X	C051	BJ	W1103	244B	24		77-35-11	ALL
	D	C053	2	W1092	01D	24		27-32-21	ALL
	D	C053	2	W1092	01E	24		27-32-21	ALL
	D	C054	2	W1100	085	24		74-31-21	ALL
	D	C055	2	W1092	300	24		27-58-11	ALL
	D	C055	2	W1100	085	24		74-31-21	ALL
	F	C056	2	W1100	286B	24		36-23-21	156-162, 166-199, 277-299
	F	C064	2	W1092	202B	24		21-31-11	ALL
	F	C064	2	W1100	269B	24		21-31-11	ALL
	F	C066	2	W1092	201R	24		21-31-11	ALL
	F	C066	2	W1103	290R	24		21-31-11	ALL
	F	C067	2	W1092	184	24		32-09-12	ALL
	F	C067	2	W1100	065	24		32-09-12	ALL
	F	C068	2	W1092	278B	24		78-36-21	ALL
	F	C068	2	W1100	226B	24		78-36-21	ALL
	F	C069	2	W1092	679	22		34-45-13	050-099, 153-156, 162-166
	F	C069	2	W1103	603	22		34-45-13	153-154
	F	C070	2	W1092	276B	24		78-36-21	ALL
	F	C070	2	W1100	224B	24		78-36-21	ALL
	F	C071	2	W1092	275B	24		78-36-21	ALL
	F	C071	2	W1100	223B	24		78-36-21	ALL
	F	C073	2	W1092	175	24		78-36-21	ALL
	F	C073	2	W1100	051	24		78-36-21	ALL
	F	C079	2	W1092	182	24		32-09-12	ALL
	F	C079	2	W1100	063	24		32-09-12	ALL
	F	C080	2	W1092	277B	24		78-36-21	ALL
	F	C080	2	W1100	225B	24		78-36-21	ALL
	F	C081	2	W1092	270R	24		78-34-21	ALL
	F	C081	2	W1100	222R	24		78-34-21	ALL
	F	C082	2	W1092	269R	24		78-34-21	ALL

## TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 129

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	F	C082	2	W1100	221R	24		78-34-21	ALL
	D	C085	2	W1092	737	22		29-11-32	ALL
	F	C088	2	W1092	132	24		31-31-13	ALL
	F	C088	2	W1103	048	24		31-31-13	ALL
	F	C089	2	W1092	130	24		31-31-13	ALL
	F	C089	2	W1103	046	24		31-31-13	ALL
	F	C090	2	W1092	128	24		31-31-13	ALL
	F	C090	2	W1103	044	24		31-31-13	ALL
	D	C092	2	W1092	023	24		21-31-11	ALL
	F	C093	2	W1092	679	22		34-45-13	150-152, 275-276
	F	C095	2	W1092	206R	24		21-31-11	ALL
	F	C095	2	W1098	201R	24		21-31-11	ALL
	F	C096	2	W1092	262R	24		32-09-12	ALL
	F	C096	2	W1100	261R	24		32-09-12	ALL
	F	C097	2	W1092	590	24		32-09-12	ALL
	F	C097	2	W1100	111	24		32-09-12	ALL
	F	C102	2	W1100	274B	24		34-22-19	ALL
	F	C102	2	W1103	243B	24		34-22-19	ALL
	F	C103	2	W1092	670B	24		73-21-14	ALL
	F	C103	2	W1100	275B	24		73-21-14	ALL
	F	C105	2	W1092	627B	22		21-31-11	ALL
	F	C105	2	W1098	214B	20		21-31-11	ALL
	F	C115	2	W1100	273B	24		34-22-18	ALL
	F	C115	2	W1103	240B	24		34-22-18	ALL
	F	C126	2	W1092	751	24		31-31-21	ALL
	F	C126	2	W1103	053	24		31-31-21	ALL
	F	C138	2	W1092	252B	24		32-61-13	ALL
	F	C138	2	W1100	214B	24		32-61-13	ALL
	F	C139	2	W1092	251B	24		32-61-13	ALL
	F	C139	2	W1100	213B	24		32-61-13	ALL
	F	C140	2	W1092	250B	24		32-61-13	ALL
	F	C140	2	W1100	212B	24		32-61-13	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 130

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	F	C144	2	W1096	207B	24		34-22-18	ALL
	F	C144	2	W1103	221B	24		34-22-18	ALL
	F	C150	2	W1100	227B	24		22-41-11	ALL
	F	C150	2	W1103	283B	24		22-41-11	ALL
	F	C151	2	W1100	228B	24		22-41-11	ALL
	F	C151	2	W1103	285B	24		22-41-11	ALL
	F	C153	2	W1100	260B	24		22-12-21	ALL
	F	C153	2	W1103	237B	24		22-12-21	ALL
	F	C158	2	W1096	203B	24		22-41-11	ALL
	F	C158	2	W1103	288B	24		22-41-11	ALL
	Y	C159	BJ	W1103	223B	24		34-61-16	ALL
	Y	C159	BJ	W1103	275B	24		34-22-38	ALL
	Y	C159	BJ	W1103	277B	24		34-61-16	ALL
	F	C163	2	W1096	202B	24		22-12-31	ALL
	F	C163	2	W1103	234B	24		22-12-31	ALL
	F	C165	2	W1092	260B	24		32-61-13	ALL
	F	C165	2	W1100	211B	24		32-61-13	ALL
	D	C166	2	W1092	0AR	24		27-81-21	ALL
	F	C167	2	W1092	258B	24		32-09-12	ALL
	F	C167	2	W1100	210B	24		32-09-12	ALL
	F	C168	2	W1092	257B	24		32-09-12	ALL
	F	C168	2	W1100	209B	24		32-09-12	ALL
	D	C171	2	W1092	01E	24		27-32-21	ALL
	D	C172	2	W1092	028	22		78-34-11	ALL
	D	C173	2	W1092	029	24		78-34-11	ALL
	D	C174	2	W1092	169	22		78-34-21	ALL
	D	C175	2	W1092	170	24		78-34-21	ALL
	F	C176	2	W1092	248B	24		32-61-12	ALL
	F	C176	2	W1100	207B	24		32-61-12	ALL
	F	C177	2	W1092	247B	24		32-61-12	ALL
	F	C177	2	W1100	206B	24		32-61-12	ALL
	F	C178	2	W1092	246B	24		32-61-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 131

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	F	C178	2	W1100	205B	24		32-61-12	ALL
	D	C179	2	W1092	706	24		32-61-14	ALL
	D	C179	2	W1092	746	24		32-61-14	ALL
	D	C180	2	W1092	709	24		32-61-14	ALL
	D	C180	2	W1092	747	24		32-61-14	ALL
	F	C181	2	W1092	074	24		32-61-14	ALL
	F	C181	2	W1100	118	24		32-61-14	ALL
	D	C183	2	W1092	708	24		32-61-14	ALL
	D	C183	2	W1092	742	24		32-61-14	ALL
	D	C184	2	W1092	711	24		32-61-14	ALL
	D	C184	2	W1092	744	24		32-61-14	ALL
	D	C185	2	W1092	067	24		32-61-14	ALL
	D	C185	2	W1092	139	24		32-61-14	ALL
	D	C186	2	W1092	058	24		32-61-14	ALL
	D	C186	2	W1092	138	24		32-61-14	ALL
	D	C187	2	W1092	053	24		32-61-14	ALL
	D	C187	2	W1092	062	24		32-61-14	ALL
	D	C188	2	W1092	021	24		32-61-14	ALL
	D	C188	2	W1092	061	24		32-61-14	ALL
	R	C189	2	W1092	057	24		24-11-11	ALL
	R	C189	2	W1092	094	24		24-11-11	ALL
	D	C190	2	W1092	01A	24		27-32-11	ALL
	D	C191	2	W1092	575	24		32-42-11	ALL
	D	C191	2	W1103	086	22		34-46-12	ALL
	D	C192	2	W1092	578	24		32-42-11	ALL
	D	C192	2	W1092	762	24		32-71-11	150-199, 275-299
	D	C193	2	W1092	578	24		32-42-11	ALL
	D	C193	2	W1100	124	24		32-61-14	ALL
	D	C194	2	W1092	088	22		33-37-21	ALL
	D	C195	2	W1092	089	22		33-37-21	ALL
	D	C196	2	W1092	575	24		32-42-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 132

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	D	C196	2	W1092	792	24		32-61-14	050-099, 150-152, 155-199, 275-299
	D	C196	2	W1100	125	24		32-61-14	153-154
	D	C197	2	W1092	572	22		33-37-11	ALL
	X	D044	BJ	W1096	209R	22		32-45-14	050-099, 150-199
	X	D044	BJ	W1100	283R	22		32-45-14	050-099, 150-199
	X	D045	BJ	W1096	211Z			32-45-14	050-099, 150-199
	X	D045	BJ	W1100	285Z			32-45-14	050-099, 150-199
	X	D046	BJ	W1096	211R	22		32-45-14	050-099, 150-199
	X	D046	BJ	W1100	285R	22		32-45-14	050-099, 150-199
	X	D050	BJ	W1092	669	24		31-31-22	ALL
	X	D050	BJ	W1103	146	24		31-31-22	ALL
	X	D051	BJ	W1092	659R	24		77-35-11	ALL
	X	D051	BJ	W1103	244R	24		77-35-11	ALL
	G	DED		W1090	004Z			24-11-11	ALL
	G	DED		W1092	002Z			27-88-11	ALL
	D	DED		W1092	028Z			78-34-11	ALL
	D	DED		W1092	029Z			78-34-11	ALL
	F	DED		W1092	052Z			78-36-11	ALL
	G	DED		W1092	054Z			29-11-32	ALL
	D	DED		W1092	059Z			32-61-14	ALL
	G	DED		W1092	063Z			32-61-14	ALL
	F	DED		W1092	087Z			33-24-11	ALL
	F	DED		W1092	102Z			24-11-11	ALL
	F	DED		W1092	153Z			32-42-11	ALL
	F	DED		W1092	172Z			78-36-11	ALL
	F	DED		W1092	174Z			78-36-11	ALL
	F	DED		W1092	180Z			32-09-12	ALL
	F	DED		W1092	182Z			32-09-12	ALL
	F	DED		W1092	183Z			32-09-12	ALL
	F	DED		W1092	184Z			32-09-12	ALL
	D	DED		W1092	563Z			78-34-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 133

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	D	DED		W1092	564Z			78-34-11	ALL
	G	DED		W1092	568Z			32-09-11	ALL
	F	DED		W1092	590Z			32-09-12	ALL
	G	DED		W1092	707Z			32-61-14	ALL
	D	DED		W1092	708Z			32-61-14	ALL
	G	DED		W1092	710Z			32-61-14	ALL
	D	DED		W1092	711Z			32-61-14	ALL
	H	DED		W1092	715Z			32-61-14	ALL
	H	DED		W1092	716Z			32-61-14	ALL
	G	DED		W1092	722Z			32-09-11	ALL
	D	DED		W1092	737Z			29-11-32	ALL
	D	DED		W1092	738Z			32-61-14	ALL
	G	DED		W1092	739Z			32-61-14	ALL
	D	DED		W1092	742Z			32-61-14	ALL
	D	DED		W1092	743Z			32-61-14	ALL
	D	DED		W1092	744Z			32-61-14	ALL
	D	DED		W1092	745Z			32-61-14	ALL
	D	DED		W1092	792Z			32-61-14	050-099, 150-152, 155-199, 275-299
	G	DED		W1092	792Z			32-61-14	050-099, 150-152, 155-199, 275-299
	F	DED		W1100	122Z			78-36-11	ALL
	D	DED		W1100	125Z			32-61-14	050-099, 150-156, 162-166, 275-276
	G	DED		W1100	125Z			32-61-14	157, 167-199, 277-299
	F	DED		W1100	501Z			78-36-11	ALL
	F	DED		W1100	502Z			78-36-11	ALL
	F	DED		W1103	063Z			22-41-11	ALL
	H	REF		W1103	297	20		34-46-12	280-299
	H	REF		W1103	297Z			34-46-12	280-299
	Y	REF		W1103	298	20		34-45-14	050-099, 150-152, 155-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 134

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0130		284T0384 (continued)					SHELF/E01/02		ALL
TB0130	D	DIODEBLOCK-REF284T0112-R33-R62-R64- (continued)					SHELF/E01/02		ALL
TB0130	F	BACM15C1A (continued)					SHELF/E01/02		ALL
TB0130	G	BACM15C1B (continued)					SHELF/E01/02		ALL
TB0130	H	BACM15C2A (continued)					SHELF/E01/02		ALL
TB0130	R	RESISTORBLOCK-REF284T0112- (continued)					SHELF/E01/02		ALL
TB0130	X	BACM15C3A (continued)					SHELF/E01/02		ALL
TB0130	Y	BACM15C3B (continued)					SHELF/E01/02		ALL
	Y	REF		W1103	298Z			34-45-14	050-099, 150-152, 155-199, 275-299
	Y	REF		W1103	500	20		34-45-14	050-099, 150-152, 155-156, 162-166, 275-276
	Y	REF		W1103	500Z			34-45-14	050-099, 150-152, 155-156, 162-166, 275-276
	Y	REF		W1103	522	20		34-45-14	050-099, 150-152, 155-199, 275-299
	Y	REF		W1103	522Z			34-45-14	050-099, 150-152, 155-199, 275-299
TB0133		284T0384					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK					SHELF/E02/02		ALL
TB0133	F	BACM15C1A					SHELF/E02/02		ALL
TB0133	G	BACM15C1B					SHELF/E02/02		ALL
TB0133	H	BACM15C2A					SHELF/E02/02		ALL
TB0133	X	BACM15C3A					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B					SHELF/E02/02		ALL
	G	10	2	W0133	215R	24		34-61-12	ALL
	G	10	2	W0133	236R	24		34-61-23	ALL
	G	10	2	W0133	292R	24		34-61-12	ALL
	G	103	2	W0133	710	24		34-61-15	ALL
	G	103	2	W0133	711	24		34-61-15	ALL
	G	103	2	W0143	011	24		34-61-25	ALL
	Z	107	BJ	W0133	763	22		31-35-17	ALL
	Z	107	BJ	W0133	764	22		31-35-17	ALL
	Z	107	BJ	W0133	765	22		31-35-17	167-199
	Z	107	BJ	W0133	766	20		31-35-17	ALL
	Z	107	BJ	W0133	791	22		31-35-17	050-099, 150-199, 275-276
	Z	107	BJ	W0133	798	22		31-35-17	ALL
	Z	107	BJ	W0133	799	22		31-35-17	050-099, 150-199, 275-276

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 135

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	G	11	2	W0133	215B	24		34-61-12	ALL
	G	11	2	W0133	236B	24		34-61-23	ALL
	G	11	2	W0133	292B	24		34-61-12	ALL
	G	114	2	W0133	057	24		34-53-13	ALL
	G	114	2	W0143	508	24		34-53-13	ALL
	G	114	2	W0143	509	24		34-53-13	ALL
	G	115	2	W0143	017	24		34-53-13	ALL
	G	115	2	W0143	510	24		34-53-13	ALL
	G	115	2	W0143	511	24		34-53-13	ALL
	G	116	2	W0133	076	20		34-53-11	ALL
	G	116	2	W0133	077	22		34-53-11	ALL
	G	116	2	W0133	078	22		34-53-11	ALL
	G	152	2	W0133	267R	24		34-22-19	050-099, 150-199, 275-276
	G	152	2	W0133	280R	24		34-51-11	277-299
	G	152	2	W0133	585R	24		31-35-13	ALL
	G	152	2	W0133	595R	24		34-22-19	ALL
	G	153	2	W0133	267B	24		34-22-19	050-099, 150-199, 275-276
	G	153	2	W0133	280B	24		34-51-11	277-299
	G	153	2	W0133	585B	24		31-35-13	ALL
	G	153	2	W0133	595B	24		34-22-19	ALL
	G	154	2	W0133	281R	24		34-55-11	050-099, 150-156, 162-166
	Z	154	BJ	W0133	281R	24		34-55-11	157, 167-199, 275-299
	G	154	2	W0133	285R	24		34-22-19	050-099, 150-156, 162-166
	Z	154	BJ	W0133	285R	24		34-22-19	157, 167-199, 275-299
	G	154	2	W0133	509R	24		31-31-20	050-099, 150-156, 162-166
	Z	154	BJ	W0133	509R	24		31-31-20	157, 167-199, 275-299
	G	154	2	W0133	546R	24		31-35-12	050-099, 150-156, 162-166
	Z	154	BJ	W0133	546R	24		31-35-12	157, 167-199, 275-299
	Z	154	BJ	W0133	834R	24		34-61-17	157, 167-199, 275-299
	G	155	2	W0133	281B	24		34-55-11	050-099, 150-156, 162-166
	Z	155	BJ	W0133	281B	24		34-55-11	157, 167-199, 275-299
	G	155	2	W0133	285B	24		34-22-19	050-099, 150-156, 162-166

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 136

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	Z	155	BJ	W0133	285B	24		34-22-19	157, 167-199, 275-299
	G	155	2	W0133	509B	24		31-31-20	050-099, 150-156, 162-166
	Z	155	BJ	W0133	509B	24		31-31-20	157, 167-199, 275-299
	G	155	2	W0133	546B	24		31-35-12	050-099, 150-156, 162-166
	Z	155	BJ	W0133	546B	24		31-35-12	157, 167-199, 275-299
	Z	155	BJ	W0133	834B	24		34-61-17	157, 167-199, 275-299
	G	161	2	W0133	216R	24		34-61-12	ALL
	G	161	2	W0133	584R	24		31-35-13	ALL
	G	161	2	W0153	201R	24		34-61-12	ALL
	G	161	2	W0153	202R	24		34-61-22	ALL
	G	162	2	W0133	216B	24		34-61-12	ALL
	G	162	2	W0133	584B	24		31-35-13	ALL
	G	162	2	W0153	201B	24		34-61-12	ALL
	G	162	2	W0153	202B	24		34-61-22	ALL
	G	163	2	W0133	164	22		31-35-16	ALL
	G	163	2	W0133	634	22		31-35-11	ALL
	G	163	2	W0133	635	22		31-35-11	ALL
	Z	17	BJ	W0133	270R	24		31-35-11	ALL
	Z	17	BJ	W0133	777R	24		23-22-15	ALL
	Z	17	BJ	W0133	783R	24		34-61-15	ALL
	Z	17	BJ	W0133	784R	24		34-61-15	ALL
	Z	17	BJ	W0133	901R	22		23-25-13	150, 153-199
	Z	17	BJ	W0143	240R	24		34-61-15	ALL
	Z	18	BJ	W0133	270B	24		31-35-11	ALL
	Z	18	BJ	W0133	777B	24		23-22-15	ALL
	Z	18	BJ	W0133	783B	24		34-61-15	ALL
	Z	18	BJ	W0133	784B	24		34-61-15	ALL
	Z	18	BJ	W0133	901B	22		23-25-13	150, 153-199
	Z	18	BJ	W0143	240B	24		34-61-15	ALL
	G	181	2	W0133	684R	24		34-61-11	150-199
	G	181	2	W0133	775R	24		34-61-11	ALL
	G	181	2	W0133	776R	24		34-61-11	050-099, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 137

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	G	181	2	W0143	201R	24		34-61-11	ALL
	G	182	2	W0133	684B	24		34-61-11	150-199
	G	182	2	W0133	775B	24		34-61-11	ALL
	G	182	2	W0133	776B	24		34-61-11	050-099, 275-299
	G	182	2	W0143	201B	24		34-61-11	ALL
	G	185	2	W0133	165	22		34-32-11	ALL
	G	185	2	W0133	175	22		34-32-11	ALL
	G	185	2	W0133	178	24		31-31-18	ALL
	G	186	2	W0133	166	22		34-32-11	ALL
	G	186	2	W0133	176	22		34-32-11	ALL
	G	186	2	W0133	179	24		31-31-18	ALL
	G	187	2	W0133	167	22		34-32-11	ALL
	G	187	2	W0133	177	22		34-32-11	ALL
	G	187	2	W0133	180	24		31-31-18	ALL
	H	188	2	W0133	233R	24		34-61-15	ALL
	H	188	2	W0133	242R	24		22-41-11	ALL
	H	188	2	W0133	247R	24		34-61-15	ALL
	H	188	2	W0133	255R	24		34-61-15	ALL
	H	188	2	W0133	583R	24		31-35-13	ALL
	H	188	2	W0143	238R	24		34-61-26	ALL
	H	188	2	W0143	245R	24		34-61-25	ALL
	H	190	2	W0133	233B	24		34-61-15	ALL
	H	190	2	W0133	242B	24		22-41-11	ALL
	H	190	2	W0133	247B	24		34-61-15	ALL
	H	190	2	W0133	255B	24		34-61-15	ALL
	H	190	2	W0133	583B	24		31-35-13	ALL
	H	190	2	W0143	238B	24		34-61-26	ALL
	H	190	2	W0143	245B	24		34-61-25	ALL
	G	23	2	W0133	264B	24		34-51-11	050-099
	Z	23	BJ	W0133	264B	24		34-51-11	150-199, 275-299
	G	23	2	W0133	287B	24		34-61-15	050-099
	Z	23	BJ	W0133	287B	24		34-61-15	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 138

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	G	23	2	W0133	291B	24		34-55-11	050-099
	Z	23	BJ	W0133	291B	24		34-55-11	150-199, 275-299
	Z	23	BJ	W0133	836B	24		34-61-17	157, 167-199, 275-299
	Z	23	BJ	W0133	902B	24		34-53-11	275-299
	Z	23	BJ	W0143	248B	24		22-21-31	150-199, 275-299
	G	24	2	W0133	264R	24		34-51-11	050-099
	Z	24	BJ	W0133	264R	24		34-51-11	150-199, 275-299
	G	24	2	W0133	287R	24		34-61-15	050-099
	Z	24	BJ	W0133	287R	24		34-61-15	150-199, 275-299
	G	24	2	W0133	291R	24		34-55-11	050-099
	Z	24	BJ	W0133	291R	24		34-55-11	150-199, 275-299
	Z	24	BJ	W0133	836R	24		34-61-17	157, 167-199, 275-299
	Z	24	BJ	W0133	902R	24		34-53-11	275-299
	Z	24	BJ	W0143	248R	24		22-21-31	150-199, 275-299
	G	27	2	W0133	111	24		31-41-16	ALL
	G	27	2	W0133	112	24		31-51-33	ALL
	G	27	2	W0133	733	24		31-51-33	ALL
	G	28	2	W0133	011	22		34-61-13	ALL
	G	28	2	W0133	023	24		34-61-23	ALL
	G	28	2	W0133	054	22		34-51-11	ALL
	G	28	2	W0133	056	22		34-51-11	ALL
	G	29	2	W0133	214R	24		34-61-12	ALL
	G	29	2	W0133	235R	24		34-61-23	ALL
	G	29	2	W0133	261R	24		34-51-11	ALL
	G	29	2	W0133	269R	24		34-51-11	ALL
	G	30	2	W0133	214B	24		34-61-12	ALL
	G	30	2	W0133	235B	24		34-61-23	ALL
	G	30	2	W0133	261B	24		34-51-11	ALL
	G	30	2	W0133	269B	24		34-51-11	ALL
	G	31	2	W0133	055	24		34-51-11	ALL
	G	31	2	W0133	089	24		34-55-11	ALL
	G	31	2	W0133	090	24		34-55-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 139

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	H	33	2	W0133	232R	24		34-61-16	ALL
	H	33	2	W0133	234R	24		34-61-15	ALL
	H	33	2	W0133	244R	24		34-21-11	ALL
	H	33	2	W0133	288R	24		34-61-15	ALL
	H	35	2	W0133	232B	24		34-61-16	ALL
	H	35	2	W0133	234B	24		34-61-15	ALL
	H	35	2	W0133	244B	24		34-21-11	ALL
	H	35	2	W0133	288B	24		34-61-15	ALL
	Z	47	BJ	W0133	590R	24		31-36-11	ALL
	Z	47	BJ	W0133	592R	24		31-36-11	ALL
	Z	47	BJ	W0133	593R	24		31-36-11	ALL
	Z	47	BJ	W0133	594R	24		31-36-11	ALL
	Z	47	BJ	W0143	233R	24		31-36-11	ALL
	Z	48	BJ	W0133	590B	24		31-36-11	ALL
	Z	48	BJ	W0133	592B	24		31-36-11	ALL
	Z	48	BJ	W0133	593B	24		31-36-11	ALL
	Z	48	BJ	W0133	594B	24		31-36-11	ALL
	Z	48	BJ	W0143	233B	24		31-36-11	ALL
	H	57	2	W0133	547R	24		31-35-12	ALL
	H	57	2	W0133	750R	24		34-45-14	ALL
	H	57	2	W0143	213R	24		34-22-29	ALL
	H	57	2	W0143	214R	24		34-33-21	ALL
	H	57	2	W0143	239R	24		31-31-20	ALL
	H	57	2	W0143	243R	24		31-41-33	ALL
	H	59	2	W0133	547B	24		31-35-12	ALL
	H	59	2	W0133	750B	24		34-45-14	ALL
	H	59	2	W0143	213B	24		34-22-29	ALL
	H	59	2	W0143	214B	24		34-33-21	ALL
	H	59	2	W0143	239B	24		31-31-20	ALL
	H	59	2	W0143	243B	24		31-41-33	ALL
	Z	61	BJ	W0133	203R	24		34-61-11	ALL
	Z	61	BJ	W0133	204R	24		34-61-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 140

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	Z	61	BJ	W0133	207R	24		34-61-11	ALL
	Z	61	BJ	W0133	559R	24		31-35-11	ALL
	Z	61	BJ	W0133	596R	24		23-22-11	ALL
	Z	61	BJ	W0133	804R	22		23-25-13	150, 153-155, 162-165
	Z	61	BJ	W0133	804R	24		23-25-13	156-157, 166-199, 277-299
	Z	62	BJ	W0133	203B	24		34-61-11	ALL
	Z	62	BJ	W0133	204B	24		34-61-11	ALL
	Z	62	BJ	W0133	207B	24		34-61-11	ALL
	Z	62	BJ	W0133	559B	24		31-35-11	ALL
	Z	62	BJ	W0133	596B	24		23-22-11	ALL
	Z	62	BJ	W0133	804B	22		23-25-13	150, 153-155, 162-165
	Z	62	BJ	W0133	804B	24		23-25-13	156-157, 166-199, 277-299
	H	63	2	W0133	213R	24		34-61-12	ALL
	H	63	2	W0133	237R	24		34-61-23	ALL
	H	63	2	W0133	240R	24		34-61-12	ALL
	H	65	2	W0133	213B	24		34-61-12	ALL
	H	65	2	W0133	237B	24		34-61-23	ALL
	H	65	2	W0133	240B	24		34-61-12	ALL
	H	69	2	W0133	243R	24		34-12-12	ALL
	H	69	2	W0133	278R	24		34-53-11	ALL
	H	69	2	W0143	211R	24		34-53-21	ALL
	G	7	2	W0133	012	24		34-61-13	ALL
	G	7	2	W0133	022	24		34-61-23	ALL
	G	7	2	W0133	088	24		34-55-11	ALL
	G	7	2	W0133	093	24		34-55-11	ALL
	H	71	2	W0133	243B	24		34-12-12	ALL
	H	71	2	W0133	278B	24		34-53-11	ALL
	H	71	2	W0143	211B	24		34-53-21	ALL
	G	75	2	W0133	230R	24		34-61-14	ALL
	G	75	2	W0133	249R	24		31-25-11	ALL
	G	75	2	W0133	250R	24		31-25-11	ALL
	G	75	2	W0133	519R	24		31-25-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 141

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	G	76	2	W0133	230B	24		34-61-14	ALL
	G	76	2	W0133	249B	24		31-25-11	ALL
	G	76	2	W0133	250B	24		31-25-11	ALL
	G	76	2	W0133	519B	24		31-25-11	ALL
	Z	79	BJ	W0133	676	24		34-61-16	157, 167-199, 275-299
	Z	79	BJ	W0133	788	24		34-61-15	157, 167-199, 275-299
	Z	79	BJ	W0133	793	24		34-61-16	157, 167-199, 275-299
	Z	79	BJ	W0133	794	24		34-61-16	157, 167-199, 275-299
	Z	79	**	W0133	829	24		34-61-17	157
	Z	79	%	W0133	829	24		34-61-17	167-199
	Z	79	BJ	W0133	829	24		34-61-17	275-299
	Z	79	BJ	W0133	840	24		34-61-27	157, 167-199, 275-299
	Z	80	BJ	W0133	245R	24		34-22-18	ALL
	Z	80	BJ	W0133	283R	24		34-61-15	ALL
	Z	80	BJ	W0133	284R	24		31-31-14	ALL
	Z	80	BJ	W0133	543R	24		31-35-12	ALL
	Z	80	BJ	W0133	845R	24		34-61-15	157, 167-199
	Z	80	BJ	W0143	220R	24		34-61-26	050-099, 150-156, 162-166
	Z	81	BJ	W0133	245B	24		34-22-18	ALL
	Z	81	BJ	W0133	283B	24		34-61-15	ALL
	Z	81	BJ	W0133	284B	24		31-31-14	ALL
	Z	81	BJ	W0133	543B	24		31-35-12	ALL
	Z	81	BJ	W0133	845B	24		34-61-15	157, 167-199
	Z	81	BJ	W0143	220B	24		34-61-26	050-099, 150-156, 162-166
	Z	82	BJ	W0133	212R	24		34-61-12	ALL
	Z	82	BJ	W0133	217R	24		34-61-12	ALL
	Z	82	BJ	W0133	238R	24		34-61-23	ALL
	Z	82	BJ	W0133	295R	24		31-31-14	ALL
	Z	82	BJ	W0133	544R	24		31-35-12	ALL
	Z	82	BJ	W0133	669R	24		34-61-16	ALL
	Z	83	BJ	W0133	212B	24		34-61-12	ALL
	Z	83	BJ	W0133	217B	24		34-61-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 142

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	Z	83	BJ	W0133	238B	24		34-61-23	ALL
	Z	83	BJ	W0133	295B	24		31-31-14	ALL
	Z	83	BJ	W0133	544B	24		31-35-12	ALL
	Z	83	BJ	W0133	669B	24		34-61-16	ALL
	G	87	2	W0133	013	24		34-61-14	ALL
	G	87	2	W0133	161	24		34-61-14	ALL
	G	87	2	W0133	162	24		34-61-14	ALL
	H	89	2	W0133	048	24		34-12-61	ALL
	H	89	2	W0133	065	24		34-21-11	ALL
	H	89	2	W0133	692	24		34-53-11	ALL
	H	89	2	W0133	725	24		34-16-11	ALL
	G	91	2	W0133	732	24		31-51-31	167-199
	G	91	2	W0133	822	24		34-61-27	157, 167-199, 277-299
	G	91	2	W0133	823	24		34-61-27	157, 167-199, 277-299
	G	91	2	W0133	827	24		31-51-31	167-199
	G	91	2	W0133	848	24		34-61-27	157, 277-299
	F	A001	2	W0133	301R	24		23-51-12	ALL
	F	A001	2	W0133	302R	24		23-51-12	ALL
	F	A002	2	W0133	293R	24		23-51-12	ALL
	F	A002	2	W0133	301Y	24		23-51-12	ALL
	Y	A003	BJ	W0133	259R	24		34-61-15	157, 167-199, 275-299
	Y	A003	BJ	W0133	845R	24		34-61-15	157, 167-199
	Y	A003	BJ	W0143	220R	24		34-61-26	157, 167-199, 277-299
	Y	A014	BJ	W0133	699	22		SPARE	153-154
	Y	A019	BJ	W0133	779	24		34-61-15	ALL
	Y	A019	BJ	W0133	780	24		34-61-15	ALL
	Y	A019	BJ	W0133	781	24		34-61-15	ALL
	Y	A03	BJ	W0143	220R	24		34-61-26	275-276
	F	A037	2	W0133	206R	24		34-61-11	ALL
	F	A037	2	W0143	208R	24		34-61-11	ALL
	X	A038	BJ	W0133	549R	24		31-35-12	ALL
	X	A038	BJ	W0143	506R	24		31-35-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 143

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	X	A039	BJ	W0133	551R	24		31-35-12	ALL
	X	A039	BJ	W0143	551R	24		31-35-12	ALL
	Y	A041	BJ	W0133	661	24		34-53-12	ALL
	Y	A041	BJ	W0133	693	24		34-53-12	ALL
	Y	A041	BJ	W0133	694	24		34-53-12	ALL
	X	A049	BJ	W0133	575R	24		31-35-13	ALL
	X	A049	BJ	W0143	227R	24		31-35-13	ALL
	X	A050	BJ	W0133	577R	24		31-35-13	ALL
	X	A050	BJ	W0143	229R	24		31-35-13	ALL
	X	A052	BJ	W0133	580R	24		31-35-13	ALL
	X	A052	BJ	W0143	231R	24		31-35-13	ALL
	Y	A077	BJ	W0133	598R	24		34-61-14	ALL
	Y	A077	BJ	W0133	599R	24		34-61-14	ALL
	Y	A077	BJ	W0143	237R	24		34-61-26	ALL
	Y	A078	BJ	W0133	676	24		34-61-16	050-099, 150-156, 162-166
	Y	A078	BJ	W0133	677	24		34-61-16	150-154
	Y	A078	BJ	W0133	679	24		34-61-16	150-154
	Y	A078	BJ	W0133	788	24		34-61-15	050-099, 150-156, 162-166
	Y	A078	BJ	W0133	793	24		34-61-16	050-099, 155-156, 162-166
	Y	A078	BJ	W0133	794	24		34-61-16	050-099, 155-156, 162-166
	X	A085	BJ	W0133	561R	24		31-35-12	050-099, 155-199, 275-299
	X	A085	BJ	W0143	501R	24		31-35-12	050-099, 155-199, 275-299
	X	A086	BJ	W0133	548R	24		31-35-12	050-099, 155-199, 275-299
	X	A086	BJ	W0143	503R	24		31-35-12	050-099, 155-199, 275-299
	D	A092	2	W0133	793	24		34-61-16	050-099, 155-199, 275-299
	D	A093	2	W0133	794	24		34-61-16	050-099, 155-199, 275-299
	D	A094	2	W0133	788	24		34-61-15	ALL
	D	A095	2	W0133	828	24		34-61-27	157, 167-199, 275-299
	D	A095	2	W0133	830	24		34-61-17	157, 167-199, 275-299
	D	A096	2	W0133	833	24		34-61-17	157, 167-199, 275-299
	X	A105	BJ	W0133	758	22		31-35-17	ALL
	X	A105	BJ	W0133	798	22		31-35-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 144

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	X	A106	BJ	W0133	760	22		31-35-17	ALL
	X	A106	BJ	W0133	799	22		31-35-17	050-099, 150-199, 275-276
	Y	A129	BJ	W0133	257R	24		34-46-11	ALL
	Y	A129	BJ	W0133	298R	24		34-46-11	ALL
	Y	A129	BJ	W0133	673R	24		34-46-11	ALL
	Y	A130	BJ	W0133	241R	24		22-32-11	ALL
	Y	A130	BJ	W0133	674R	24		34-61-15	ALL
	Y	A130	BJ	W0133	682R	24		34-61-16	ALL
	Y	A130	BJ	W0143	232R	24		34-61-26	ALL
	X	A141	BJ	W0133	553R	24		31-35-12	050-099, 155-199, 275-299
	X	A141	BJ	W0143	553R	24		31-35-12	050-099, 155-199, 275-299
	X	A142	BJ	W0133	555R	24		31-35-12	050-099, 155-199, 275-299
	X	A142	BJ	W0143	555R	24		31-35-12	050-099, 155-199, 275-299
	X	A148	BJ	W0133	170	24		31-35-16	ALL
	X	A149	BJ	W0133	174	24		31-35-16	ALL
	X	A150	BJ	W0133	196	24		31-35-16	ALL
	X	A157	BJ	W0133	553R	24		31-35-12	150-154
	X	A157	BJ	W0143	553R	24		31-35-12	150-154
	X	A158	BJ	W0133	555R	24		31-35-12	150-154
	X	A158	BJ	W0143	555R	24		31-35-12	150-154
	X	A159	BJ	W0133	271R	24		31-35-11	ALL
	X	A159	BJ	W0143	221R	24		31-35-11	ALL
	X	A160	BJ	W0133	562R	24		31-35-12	150-154
	X	A160	BJ	W0143	502R	24		31-35-12	150-154
	Y	A164	BJ	W0133	540R	24		31-35-11	ALL
	Y	A164	BJ	W0133	541R	24		31-35-11	ALL
	Y	A164	BJ	W0143	226R	24		31-35-11	ALL
	F	A171	2	W0133	218R	24		34-61-13	ALL
	F	A171	2	W0143	202R	24		34-61-13	ALL
	F	A172	2	W0133	219R	24		34-61-13	ALL
	F	A172	2	W0143	203R	24		34-61-13	ALL
	F	A173	2	W0133	220R	24		34-61-13	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 145

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	F	A173	2	W0143	204R	24		34-61-13	ALL
	F	A174	2	W0133	221R	24		34-61-13	ALL
	F	A174	2	W0143	205R	24		34-61-13	ALL
	F	A175	2	W0133	010	24		34-61-13	ALL
	F	A175	2	W0143	001	24		34-61-13	ALL
	F	A177	2	W0133	201R	24		34-61-11	ALL
	F	A177	2	W0143	210R	24		34-61-11	ALL
	D	A192	2	W0133	823	24		34-61-27	157, 167-199, 277-299
	D	A193	2	W0133	827	24		31-51-31	157, 277-299
	D	A193	2	W0133	848	24		34-61-27	157, 277-299
	X	B038	BJ	W0133	549B	24		31-35-12	ALL
	X	B038	BJ	W0143	506B	24		31-35-12	ALL
	X	B039	BJ	W0133	551B	24		31-35-12	ALL
	X	B039	BJ	W0143	551B	24		31-35-12	ALL
	X	B049	BJ	W0133	575B	24		31-35-13	ALL
	X	B049	BJ	W0143	227B	24		31-35-13	ALL
	X	B050	BJ	W0133	577B	24		31-35-13	ALL
	X	B050	BJ	W0143	229B	24		31-35-13	ALL
	X	B052	BJ	W0133	580B	24		31-35-13	ALL
	X	B052	BJ	W0143	231B	24		31-35-13	ALL
	X	B085	BJ	W0133	561B	24		31-35-12	050-099, 155-199, 275-299
	X	B085	BJ	W0143	501B	24		31-35-12	050-099, 155-199, 275-299
	X	B086	BJ	W0133	548B	24		31-35-12	050-099, 155-199, 275-299
	X	B086	BJ	W0143	503B	24		31-35-12	050-099, 155-199, 275-299
	X	B105	BJ	W0133	753	22		31-35-17	050-099, 155-199, 275-299
	X	B106	BJ	W0133	756	22		31-35-17	ALL
	X	B106	BJ	W0133	764	22		31-35-17	ALL
	X	B141	BJ	W0133	553B	24		31-35-12	050-099, 155-199, 275-299
	X	B141	BJ	W0143	553B	24		31-35-12	050-099, 155-199, 275-299
	X	B142	BJ	W0133	555B	24		31-35-12	050-099, 155-199, 275-299
	X	B142	BJ	W0143	555B	24		31-35-12	050-099, 155-199, 275-299
	X	B148	BJ	W0133	171	24		31-35-16	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 146

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	X	B148	BJ	W0133	665	24		31-35-16	ALL
	X	B149	BJ	W0133	192	24		31-35-16	ALL
	X	B149	BJ	W0133	666	24		31-35-16	ALL
	X	B150	BJ	W0133	197	24		31-35-16	ALL
	X	B157	BJ	W0133	553B	24		31-35-12	150-154
	X	B157	BJ	W0143	553B	24		31-35-12	150-154
	X	B158	BJ	W0133	555B	24		31-35-12	150-154
	X	B158	BJ	W0143	555B	24		31-35-12	150-154
	X	B159	BJ	W0133	271B	24		31-35-11	ALL
	X	B159	BJ	W0143	221B	24		31-35-11	ALL
	X	B160	BJ	W0133	562B	24		31-35-12	150-154
	X	B160	BJ	W0143	502B	24		31-35-12	150-154
	F	C001	2	W0133	301B	24		23-51-12	ALL
	F	C001	2	W0133	302B	24		23-51-12	ALL
	F	C002	2	W0133	293B	24		23-51-12	ALL
	F	C002	2	W0133	302Y	24		23-51-12	ALL
	Y	C003	BJ	W0133	259B	24		34-61-15	157, 167-199, 275-299
	Y	C003	BJ	W0133	845B	24		34-61-15	157, 167-199
	Y	C003	BJ	W0143	220B	24		34-61-26	157, 167-199, 277-299
	Y	C03	BJ	W0143	220B	24		34-61-26	275-276
	F	C037	2	W0133	206B	24		34-61-11	ALL
	F	C037	2	W0143	208B	24		34-61-11	ALL
	X	C038	BJ	W0133	550R	24		31-35-12	ALL
	X	C038	BJ	W0143	507R	24		31-35-12	ALL
	X	C039	BJ	W0133	552R	24		31-35-12	ALL
	X	C039	BJ	W0143	552R	24		31-35-12	ALL
	X	C049	BJ	W0133	576R	24		31-35-13	ALL
	X	C049	BJ	W0143	228R	24		31-35-13	ALL
	X	C050	BJ	W0133	578R	24		31-35-13	ALL
	X	C050	BJ	W0143	230R	24		31-35-13	ALL
	X	C051	BJ	W0133	579R	24		31-35-13	ALL
	X	C051	BJ	W0153	205R	24		31-35-13	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 147

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	X	C052	BJ	W0133	582R	24		31-35-13	ALL
	X	C052	BJ	W0153	207R	24		31-35-13	ALL
	Y	C077	BJ	W0133	598B	24		34-61-14	ALL
	Y	C077	BJ	W0133	599B	24		34-61-14	ALL
	Y	C077	BJ	W0143	237B	24		34-61-26	ALL
	X	C085	BJ	W0133	562R	24		31-35-12	050-099, 155-199, 275-299
	X	C085	BJ	W0143	502R	24		31-35-12	050-099, 155-199, 275-299
	X	C086	BJ	W0133	538R	24		31-31-20	155-199, 275-299
	X	C086	BJ	W0133	542R	24		31-35-12	050-099, 155-199, 275-299
	D	C092	2	W0133	792	24		34-61-16	050-099, 155-199, 275-299
	D	C093	2	W0133	795	24		34-61-16	050-099, 155-199, 275-299
	D	C094	2	W0133	787	24		34-61-15	ALL
	D	C095	2	W0133	831	24		34-61-17	157, 167-199, 275-299
	D	C096	2	W0133	832	24		34-61-17	157, 167-199, 275-299
	X	C105	BJ	W0133	759	22		31-35-17	ALL
	X	C105	BJ	W0133	791	22		31-35-17	050-099, 150-199, 275-276
	X	C106	BJ	W0133	761	22		31-35-17	ALL
	Y	C129	BJ	W0133	257B	24		34-46-11	ALL
	Y	C129	BJ	W0133	298B	24		34-46-11	ALL
	Y	C129	BJ	W0133	673B	24		34-46-11	ALL
	Y	C130	BJ	W0133	241B	24		22-32-11	ALL
	Y	C130	BJ	W0133	674B	24		34-61-15	ALL
	Y	C130	BJ	W0133	682B	24		34-61-16	ALL
	Y	C130	BJ	W0143	232B	24		34-61-26	ALL
	X	C141	BJ	W0133	554R	24		31-35-12	050-099, 155-199, 275-299
	X	C141	BJ	W0143	554R	24		31-35-12	050-099, 155-199, 275-299
	X	C148	BJ	W0133	172	24		31-35-16	ALL
	X	C148	BJ	W0133	665	24		31-35-16	ALL
	X	C149	BJ	W0133	193	24		31-35-16	ALL
	X	C157	BJ	W0133	554R	24		31-35-12	150-154
	X	C157	BJ	W0143	554R	24		31-35-12	150-154
	X	C158	BJ	W0133	538R	24		31-31-20	050-099, 150-154

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 148

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	X	C158	BJ	W0133	542R	24		31-35-12	150-154
	X	C159	BJ	W0133	561R	24		31-35-12	150-154
	X	C159	BJ	W0143	501R	24		31-35-12	150-154
	X	C160	BJ	W0133	548R	24		31-35-12	150-154
	X	C160	BJ	W0143	503R	24		31-35-12	150-154
	Y	C164	BJ	W0133	540B	24		31-35-11	ALL
	Y	C164	BJ	W0133	541B	24		31-35-11	ALL
	Y	C164	BJ	W0143	226B	24		31-35-11	ALL
	F	C171	2	W0133	218B	24		34-61-13	ALL
	F	C171	2	W0143	202B	24		34-61-13	ALL
	F	C172	2	W0133	219B	24		34-61-13	ALL
	F	C172	2	W0143	203B	24		34-61-13	ALL
	F	C173	2	W0133	220B	24		34-61-13	ALL
	F	C173	2	W0143	204B	24		34-61-13	ALL
	F	C174	2	W0133	221B	24		34-61-13	ALL
	F	C174	2	W0143	205B	24		34-61-13	ALL
	F	C177	2	W0133	201B	24		34-61-11	ALL
	F	C177	2	W0143	210B	24		34-61-11	ALL
	F	C180	2	W0133	027	22		34-61-13	ALL
	F	C180	2	W0143	002	22		34-61-13	ALL
	D	C192	2	W0133	824	24		34-61-27	157, 167-199, 277-299
	D	C193	2	W0133	732	24		31-51-31	157, 277-299
	X	D038	BJ	W0133	550B	24		31-35-12	ALL
	X	D038	BJ	W0143	507B	24		31-35-12	ALL
	X	D039	BJ	W0133	552B	24		31-35-12	ALL
	X	D039	BJ	W0143	552B	24		31-35-12	ALL
	X	D049	BJ	W0133	576B	24		31-35-13	ALL
	X	D049	BJ	W0143	228B	24		31-35-13	ALL
	X	D050	BJ	W0133	578B	24		31-35-13	ALL
	X	D050	BJ	W0143	230B	24		31-35-13	ALL
	X	D051	BJ	W0133	579B	24		31-35-13	ALL
	X	D051	BJ	W0153	205B	24		31-35-13	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 149

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	X	D052	BJ	W0133	582B	24		31-35-13	ALL
	X	D052	BJ	W0153	207B	24		31-35-13	ALL
	X	D085	BJ	W0133	562B	24		31-35-12	050-099, 155-199, 275-299
	X	D085	BJ	W0143	502B	24		31-35-12	050-099, 155-199, 275-299
	X	D086	BJ	W0133	538B	24		31-31-20	155-199, 275-299
	X	D086	BJ	W0133	542B	24		31-35-12	050-099, 155-199, 275-299
	X	D105	BJ	W0133	754	22		31-35-17	ALL
	X	D105	BJ	W0133	763	22		31-35-17	ALL
	X	D106	BJ	W0133	757	22		31-35-17	ALL
	X	D106	BJ	W0133	765	22		31-35-17	167-199
	X	D141	BJ	W0133	554B	24		31-35-12	050-099, 155-199, 275-299
	X	D141	BJ	W0143	554B	24		31-35-12	050-099, 155-199, 275-299
	X	D148	BJ	W0133	173	24		31-35-16	ALL
	X	D148	BJ	W0133	666	24		31-35-16	ALL
	X	D149	BJ	W0133	195	24		31-35-16	ALL
	X	D157	BJ	W0133	554B	24		31-35-12	150-154
	X	D157	BJ	W0143	554B	24		31-35-12	150-154
	X	D158	BJ	W0133	538B	24		31-31-20	050-099, 150-154
	X	D158	BJ	W0133	542B	24		31-35-12	150-154
	X	D159	BJ	W0133	561B	24		31-35-12	150-154
	X	D159	BJ	W0143	501B	24		31-35-12	150-154
	X	D160	BJ	W0133	548B	24		31-35-12	150-154
	X	D160	BJ	W0143	503B	24		31-35-12	150-154
	F	DED		W0133	010Z			34-61-13	ALL
	F	DED		W0133	027Z			34-61-13	ALL
	G	DED		W0133	057Z			34-53-13	ALL
	G	DED		W0133	076Z			34-53-11	ALL
	Y	DED		W0133	598Z			34-61-14	150-154, 277-299
	Y	DED		W0133	676Z			34-61-16	050-099, 150-156, 162-166, 275-276, 280-299
	Z	DED		W0133	676Z			34-61-16	157, 167-199, 277-278
	G	DED		W0133	775Z			34-61-11	150-154

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 150

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0133		284T0384 (continued)					SHELF/E02/02		ALL
TB0133	D	DIODEBLOCK (continued)					SHELF/E02/02		ALL
TB0133	F	BACM15C1A (continued)					SHELF/E02/02		ALL
TB0133	G	BACM15C1B (continued)					SHELF/E02/02		ALL
TB0133	H	BACM15C2A (continued)					SHELF/E02/02		ALL
TB0133	X	BACM15C3A (continued)					SHELF/E02/02		ALL
TB0133	Y	BACM15C3B (continued)					SHELF/E02/02		ALL
TB0133	Z	BACM15C3B (continued)					SHELF/E02/02		ALL
	Z	DED		W0133	845Z			34-61-15	157, 167-199
	X	REF		W0133	271	20		31-35-11	050-099, 155-199, 275-299
	X	REF		W0133	271Z			31-35-11	050-099, 155-199, 275-299
	Z	REF		W0133	669	20		34-61-16	050-099, 155-199, 275-299
	Z	REF		W0133	669Z			34-61-16	050-099, 155-199, 275-299
	H	REF		W0133	750	20		34-45-14	050-099, 155-199, 275-299
	H	REF		W0133	750Z			34-45-14	050-099, 155-199, 275-299
	H	REF		W0143	213	20		34-22-29	050-099, 150-151, 155-199
	H	REF		W0143	213Z			34-22-29	050-099, 150-151, 155-199
	H	REF		W0143	214	20		34-33-21	050-099, 155-199, 277-299
	H	REF		W0143	214Z			34-33-21	050-099, 155-199, 277-299
	X	REF		W0143	221	20		31-35-11	050-099, 155-199, 275-299
	X	REF		W0143	221Z			31-35-11	050-099, 155-199, 275-299
	H	REF		W0143	243	20		31-41-33	050-099, 155-199, 277-299
	H	REF		W0143	243Z			31-41-33	050-099, 155-199, 277-299
TB0139		284T0116-1					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125-					SHELF/E02/05		ALL
TB0139	F	BACM15C1A					SHELF/E02/05		ALL
TB0139	G	BACM15C1B					SHELF/E02/05		ALL
TB0139	H	BACM15C2A					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125-					SHELF/E02/05		ALL
TB0139	X	BACM15C3A					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C					SHELF/E02/05		ALL
	Z	10	BJ	W0139	655	24		23-51-11	050-099, 150-199
	Z	10	BJ	W0139	659	24		23-51-11	050-099, 150-199
	Z	10	BJ	W0139	664	24		23-51-41	050-099, 153-199
	Z	10	BJ	W0149	006	24		23-31-11	050-099, 150-199
	Z	10	BJ	W0149	303Y	24		23-51-11	050-099, 150-199
	Z	10	BJ	W0149	508	24		23-31-11	050-099, 150-199
	Z	10	BJ	W0149	521	24		23-31-11	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 151

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	H	101	2	W0149	003	18		23-31-11	050-099, 150-199
	G	101	2	W0149	003	18		23-31-11	275-299
	H	101	2	W0149	004	20		23-31-11	050-099, 150-199
	G	101	2	W0149	004	20		23-31-11	275-299
	H	101	2	W0149	005	20		23-31-11	050-099, 150-199
	G	101	2	W0149	005	20		23-31-11	275-299
	G	101	2	W0149	141	20		23-31-12	275-299
	H	101	2	W0149	197	20		23-31-11	050-099, 150-199
	H	101	2	W0149	199	20		23-31-13	050-099, 150-199
	H	101	2	W0149	522	20		23-31-11	050-099, 150-199
	H	101	2	W0149	560	20		23-31-14	050-099, 150-199
	G	104	2	W0139	096	24		23-31-13	ALL
	G	104	2	W0149	021	24		23-31-13	ALL
	G	104	2	W0149	029	24		23-32-12	ALL
	G	104	2	W0149	145	24		23-31-12	275-299
	G	106	2	W0139	095	24		23-31-13	050-099, 150-199
	G	106	2	W0149	020	24		23-31-13	050-099, 150-199
	G	106	2	W0149	507	24		23-31-11	050-099, 150-199
	G	107	2	W0139	097	22		23-34-11	ALL
	G	107	2	W0149	038	22		23-34-11	ALL
	G	108	2	W0139	775	22		23-34-11	ALL
	G	108	2	W0149	040	22		23-34-11	ALL
	G	108	2	W0149	811	24		23-34-13	050-099
	G	108	2	W0149	812	24		23-34-13	050-099
	G	109	2	W0149	007	24		23-31-11	050-099
	G	109	2	W0149	509	24		23-31-11	050-099
	G	109	2	W0149	510	24		23-31-11	050-099
	Z	11	BJ	W0139	116	24		23-51-11	050-099, 150-199
	H	11	2	W0139	116	24		23-51-11	275-299
	Z	11	BJ	W0139	143	24		23-51-21	050-099, 150-199
	H	11	2	W0139	143	24		23-51-21	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 152

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	Z	11	BJ	W0139	167	24		23-51-41	050-099, 150-199
	H	11	2	W0139	167	24		23-51-41	275-299
	Z	11	BJ	W0149	237R	24		23-51-11	050-099, 150-199
	H	11	2	W0149	237R	24		23-51-11	275-299
	G	110	2	W0149	524	24		23-31-11	050-099
	G	110	2	W0149	525	24		23-31-11	050-099
	G	110	2	W0149	549	24		23-31-14	050-099
	H	111	2	W0139	650	22		23-42-11	050-099
	H	111	2	W0149	087	22		23-42-11	050-099
	H	111	2	W0149	104	22		23-42-11	050-099
	H	111	2	W0149	622	22		23-42-11	050-099
	H	111	2	W0149	623	22		23-42-11	050-099
	G	117	2	W0149	209R	22		23-31-14	275-299
	Z	117	BJ	W0149	244R	22		23-31-14	050-099, 150-199
	G	117	2	W0149	244R	22		23-31-14	275-299
	Z	117	BJ	W0149	245R	22		23-31-14	050-099, 150-199
	G	117	2	W0149	245R	22		23-31-14	275-299
	Z	117	BJ	W0149	257R	22		23-31-14	050-099, 150-199
	Z	117	BJ	W0149	265R	22		23-31-14	050-099, 150-199
	Z	117	BJ	W0149	278R	24		23-31-13	050-099, 150-199
	Z	117	BJ	W0149	279R	24		23-31-13	050-099, 150-199
	Z	117	BJ	W0149	280R	24		23-31-13	050-099, 150-199
	G	118	2	W0149	209B	22		23-31-14	275-299
	Z	118	BJ	W0149	244B	22		23-31-14	050-099, 150-199
	G	118	2	W0149	244B	22		23-31-14	275-299
	Z	118	BJ	W0149	245B	22		23-31-14	050-099, 150-199
	G	118	2	W0149	245B	22		23-31-14	275-299
	Z	118	BJ	W0149	257B	22		23-31-14	050-099, 150-199
	Z	118	BJ	W0149	265B	22		23-31-14	050-099, 150-199
	Z	118	BJ	W0149	278B	24		23-31-13	050-099, 150-199
	Z	118	BJ	W0149	279B	24		23-31-13	050-099, 150-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 153

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	Z	118	BJ	W0149	280B	24		23-31-13	050-099, 150-199
	Z	12	BJ	W0149	555	20		23-31-14	050-099, 150-199
	Z	12	BJ	W0149	556	20		23-31-14	050-099, 150-199
	Z	12	BJ	W0149	557	20		23-31-14	050-099, 150-199
	Z	12	BJ	W0149	558	20		23-31-14	150-199
	Z	12	BJ	W0149	559	20		23-31-14	050-099, 150-199
	Z	12	BJ	W0149	560	20		23-31-14	050-099, 150-199
	Z	122	BJ	W0139	650	22		23-42-11	162-199
	G	122	2	W0149	055	24		23-34-13	050-099
	G	122	2	W0149	056	24		23-34-13	050-099
	G	122	2	W0149	057	22		23-42-12	150-157, 275-299
	Z	122	BJ	W0149	057	22		23-42-12	162-199
	G	122	2	W0149	087	22		23-42-11	150-157, 275-299
	Z	122	BJ	W0149	087	22		23-42-11	162-199
	G	122	2	W0149	104	22		23-42-11	150-157, 275-299
	Z	122	BJ	W0149	104	22		23-42-11	162-199
	G	122	2	W0149	124	24		33-25-11	050-099
	Z	122	BJ	W0149	622	22		23-42-11	162-199
	Z	122	BJ	W0149	623	22		23-42-11	162-199
	G	123	2	W0139	001	16		23-12-11	050-099, 150-157, 275-299
	G	123	2	W0139	002	18		23-12-11	050-099, 150-157, 275-299
	G	123	2	W0149	001	16		23-12-11	050-099, 150-157, 275-299
	G	125	2	W0149	265R	22		23-31-14	050-099, 150-199
	G	125	2	W0149	266R	22		23-31-14	050-099, 150-199
	G	125	2	W0149	267R	22		23-31-14	050-099, 150-199
	G	125	2	W0149	268R	22		23-31-14	050-099, 150-199
	G	126	2	W0149	265B	22		23-31-14	050-099, 150-199
	G	126	2	W0149	266B	22		23-31-14	050-099, 150-199
	G	126	2	W0149	267B	22		23-31-14	050-099, 150-199
	G	126	2	W0149	268B	22		23-31-14	050-099, 150-199
	G	127	2	W0149	209R	22		23-31-14	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 154

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	G	127	2	W0149	269R	22		23-31-14	050-099, 150-199
	G	127	2	W0149	274R	22		23-31-14	050-099, 150-199
	G	128	2	W0149	209B	22		23-31-14	050-099, 150-199
	G	128	2	W0149	269B	22		23-31-14	050-099, 150-199
	G	128	2	W0149	274B	22		23-31-14	050-099, 150-199
	G	129	2	W0139	214R	24		23-22-12	ALL
	G	129	2	W0139	282R	24		23-22-12	ALL
	G	129	2	W0139	285R	24		23-22-12	ALL
	G	130	2	W0139	214B	24		23-22-12	ALL
	G	130	2	W0139	282B	24		23-22-12	ALL
	G	130	2	W0139	285B	24		23-22-12	ALL
	G	131	2	W0139	270R	24		23-22-12	ALL
	G	131	2	W0139	283R	24		23-22-12	ALL
	G	131	2	W0139	284R	24		23-22-12	ALL
	G	131	2	W0139	286R	24		23-22-12	ALL
	G	132	2	W0139	270B	24		23-22-12	ALL
	G	132	2	W0139	283B	24		23-22-12	ALL
	G	132	2	W0139	284B	24		23-22-12	ALL
	G	132	2	W0139	286B	24		23-22-12	ALL
	H	133	2	W0149	572	24		23-31-13	050-099, 150-199
	H	133	2	W0149	573	24		23-31-13	050-099, 150-199
	H	133	2	W0149	574	24		23-31-13	050-099, 150-199
	H	133	2	W0149	808	24		23-31-12	050-099, 150-199
	G	139	2	W0149	702	24		23-34-13	280-299
	G	139	2	W0149	703	24		23-34-13	280-299
	G	139	2	W0149	704	24		23-34-13	280-299
	G	14	2	W0139	238B	24		23-51-21	ALL
	G	14	2	W0139	243B	24		23-51-41	ALL
	G	14	2	W0149	243B	24		23-51-21	ALL
	G	140	2	W0149	702	24		23-34-13	275-278
	G	140	2	W0149	703	24		23-34-13	275-278

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 155

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	G	140	2	W0149	704	24		23-34-13	275-278
	G	146	2	W0139	103	16		23-12-31	ALL
	G	146	2	W0139	104	16		23-12-31	ALL
	G	146	2	W0139	105	18		23-12-31	ALL
	G	147	2	W0139	257R	22		23-22-11	ALL
	G	147	2	W0139	269R	22		23-22-11	ALL
	G	148	2	W0139	257B	22		23-22-11	ALL
	G	148	2	W0139	269B	22		23-22-11	ALL
	G	148	2	W0149	273B	22		23-22-12	050-099, 150-199, 275-278
	G	159	2	W0139	221R	24		23-22-12	ALL
	G	159	2	W0139	222R	24		23-21-11	ALL
	G	159	2	W0139	248R	24		23-21-11	ALL
	G	16	2	W0149	550	24		23-31-14	050-099, 150-199
	G	16	2	W0149	551	24		23-31-14	050-099, 150-199
	G	16	2	W0149	9003	24		23-31-13	050-099, 150-199
	G	160	2	W0139	221B	24		23-22-12	ALL
	G	160	2	W0139	222B	24		23-21-11	ALL
	G	160	2	W0139	248B	24		23-21-11	ALL
	G	161	2	W0149	707	24		23-34-13	275-299
	G	161	2	W0149	710	24		23-34-13	275-299
	G	161	2	W0149	799	24		23-34-13	275-299
	G	162	2	W0139	058	20		23-22-11	277-299
	G	162	2	W0139	553	20		23-22-11	277-299
	G	162	2	W0139	689	20		23-22-12	275-299
	G	163	2	W0139	058	20		23-22-11	150, 152-199
	G	163	2	W0139	901	20		23-22-11	150, 152-199
	G	163	2	W0139	902	20		23-22-12	150, 152-199
	G	166	2	W0139	633	24		23-22-11	277-278
	G	166	2	W0139	692	24		23-22-11	277-278
	G	166	2	W0139	792	24		23-22-11	277-278
	G	167	2	W0139	032	24		23-21-11	050-099, 150, 152-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 156

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	G	167	2	W0139	784	24		23-21-11	050-099, 150, 152-199, 277-299
	G	167	2	W0139	793	24		23-22-11	050-099, 150, 152-199, 275-299
	G	169	2	W0139	026	24		23-21-11	150, 152-199, 277-299
	G	169	2	W0139	159	24		23-21-11	150, 152-199, 277-299
	G	169	2	W0139	670	22		23-25-14	150, 153-155, 162-165
	G	169	2	W0139	670	24		23-25-14	156-157, 166-199, 277-299
	G	170	2	W0139	088	24		23-22-12	ALL
	G	170	2	W0139	183	24		23-22-12	ALL
	G	170	2	W0139	671	24		23-22-12	167-199
	G	170	2	W0139	690	22		23-22-12	275-299
	G	170	2	W0139	708	24		23-22-12	ALL
	G	170	2	W0139	903	22		23-22-12	150, 152-166
	G	171	2	W0139	007	16		23-12-21	157, 167-199, 277-299
	G	171	2	W0139	008	18		23-12-21	157, 167-199, 277-299
	G	171	2	W0149	002	16		23-12-21	157, 167-199, 277-299
	G	178	2	W0139	018	24		23-21-11	050-099, 150-156, 162-166, 275-276
	G	178	2	W0139	051	24		23-12-11	050-099, 150-156, 162-166, 275-276
	G	178	2	W0139	782	24		31-31-17	050-099, 150-156, 162-166, 275-276
	G	179	2	W0139	019	24		23-21-11	050-099, 150-156, 162-166, 275-276
	G	179	2	W0139	052	24		23-12-21	050-099, 150-156, 162-166, 275-276
	G	179	2	W0139	781	24		31-31-17	050-099, 150-156, 162-166, 275-276
	G	18	2	W0149	043	24		23-31-11	050-099, 150-199
	G	18	2	W0149	516	24		23-31-11	050-099, 150-199
	G	18	2	W0149	523	24		23-31-11	050-099, 150-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 157

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	G	180	2	W0139	053	24		23-12-31	050-099, 150-156, 162-166, 275-276
	G	180	2	W0139	054	24		23-21-11	050-099, 150-156, 162-166, 275-276
	G	180	2	W0139	082	24		31-31-17	050-099, 150-156, 162-166, 275-276
	G	181	2	W0139	030	24		23-21-11	050-099, 150-156, 162-166, 275-276
	G	181	2	W0139	772	24		23-11-11	050-099, 150-156, 162-166, 275-276
	G	181	2	W0139	779	24		31-31-17	050-099, 150-156, 162-166, 275-276
	G	182	2	W0139	031	24		23-21-11	050-099, 150-156, 162-166, 275-276
	G	182	2	W0139	780	24		31-31-17	050-099, 150-156, 162-166, 275-276
	G	182	2	W0149	076	24		23-11-21	050-099, 150-156, 162-166, 275-276
	G	183	2	W0139	007	16		23-12-21	050-099, 150-156, 162-166, 275-276
	G	183	2	W0139	008	18		23-12-21	050-099, 150-156, 162-166, 275-276
	G	183	2	W0149	002	16		23-12-21	050-099, 150-156, 162-166, 275-276
	G	184	2	W0139	752	24		23-12-21	050-099, 150-156, 162-166, 275-276
	G	184	2	W0139	753	24		23-12-31	050-099, 150-156, 162-166, 275-276
	G	184	2	W0149	051	24		23-12-21	050-099, 150-156, 162-166, 275-276
	G	189	#	W0149	783	24		23-34-13	150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 158

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	G	189	2	W0149	789	24		23-34-13	050-099, 150-199
	G	189	2	W0149	793	24		23-34-13	275-299
	G	189	2	W0149	797	24		23-34-13	ALL
	G	189	2	W0149	801	24		23-34-13	150-154, 156-199, 275-299
	G	189	2	W0149	805	24		23-34-13	050-099, 150-154, 156-199
	G	19	2	W0149	007	24		23-31-11	150-199
	G	19	2	W0149	509	24		23-31-11	150-199
	G	19	2	W0149	510	24		23-31-11	150-199
	G	190	2	W0149	793	24		23-34-13	050-099
	G	190	2	W0149	805	24		23-34-13	050-099
	G	190	2	W0149	813	24		23-34-13	050-099
	G	191	#	W0149	785	24		23-34-13	150-199
	G	191	2	W0149	790	24		23-34-13	050-099, 150-199
	G	191	2	W0149	794	24		23-34-13	275-299
	G	191	2	W0149	798	24		23-34-13	ALL
	G	191	2	W0149	802	24		23-34-13	150-154, 156-199, 275-299
	G	191	2	W0149	804	24		23-34-13	050-099, 150-154, 156-199
	G	192	2	W0149	794	24		23-34-13	050-099
	G	192	2	W0149	802	24		23-34-13	050-099
	G	192	2	W0149	804	24		23-34-13	050-099
	G	193	2	W0149	046	24		23-34-13	050-099
	G	193	2	W0149	156	24		23-34-13	050-099
	G	193	2	W0149	157	24		23-34-13	050-099
	G	194	2	W0149	045	24		23-34-13	050-099
	G	194	2	W0149	779	24		23-34-13	050-099
	G	194	2	W0149	796	24		23-34-13	050-099
	G	195	2	W0149	801	24		23-34-13	050-099
	G	195	2	W0149	809	24		23-34-13	050-099
	G	195	2	W0149	810	24		23-34-13	050-099
	G	20	2	W0149	524	24		23-31-11	150-199
	G	20	2	W0149	525	24		23-31-11	150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 159

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	G	20	2	W0149	549	24		23-31-14	150-199
	G	21	2	W0149	008	24		23-31-11	ALL
	G	21	2	W0149	031	24		23-32-12	ALL
	G	21	2	W0149	129	24		23-31-11	275-299
	G	21	2	W0149	144	24		23-31-12	275-299
	G	21	2	W0149	900	20		23-32-21	150, 152-199
	G	21	2	W0149	9004	24		23-31-14	050-099, 150-199
	G	22	2	W0149	246R	24		23-41-11	ALL
	G	22	2	W0149	302R	24		23-41-11	ALL
	G	22	2	W0149	307R	24		23-41-11	ALL
	G	23	2	W0149	246B	24		23-41-11	ALL
	G	23	2	W0149	302B	24		23-41-11	ALL
	G	23	2	W0149	307B	24		23-41-11	ALL
	G	24	2	W0149	542	24		23-31-13	050-099, 150-199
	G	24	2	W0149	543	24		23-31-13	050-099, 150-199
	G	24	2	W0149	566	24		23-31-13	050-099, 150-199
	Z	26	BJ	W0139	743	24		23-51-13	050-099, 150-199
	H	26	2	W0139	743	24		23-51-13	275-299
	Z	26	BJ	W0139	745	24		23-51-21	050-099, 150-199
	H	26	2	W0139	745	24		23-51-21	275-299
	Z	26	BJ	W0139	746	24		23-51-41	050-099, 150-199
	H	26	2	W0139	746	24		23-51-41	275-299
	Z	26	2	W0149	260R	24		23-51-13	050-099
	Z	26	BJ	W0149	260R	24		23-51-13	150-199
	H	26	2	W0149	260R	24		23-51-13	275-299
	Z	27	BJ	W0139	121	24		23-51-12	050-099, 150-199
	Z	27	BJ	W0139	154	24		23-51-21	050-099, 150-199
	Z	27	BJ	W0139	178	24		23-51-41	050-099, 150-199
	Z	27	BJ	W0139	304R	24		23-51-12	050-099, 150-199
	G	28	2	W0139	122	24		23-51-12	050-099, 150-199
	G	28	2	W0139	150	24		23-51-21	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 160

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	G	28	2	W0139	174	24		23-51-41	050-099, 150-199
	G	28	2	W0139	304Y	24		23-51-12	050-099, 150-199
	H	29	2	W0139	121	24		23-51-12	275-299
	G	29	2	W0139	124	24		23-51-12	050-099, 150-199
	G	29	2	W0139	152	24		23-51-21	050-099, 150-199
	H	29	2	W0139	154	24		23-51-21	275-299
	G	29	2	W0139	176	24		23-51-41	050-099, 150-199
	H	29	2	W0139	178	24		23-51-41	275-299
	G	29	2	W0139	232R	24		23-51-12	050-099, 150-199
	H	29	2	W0139	304R	24		23-51-12	275-299
	G	30	2	W0149	207R	24		23-31-13	050-099, 150-199
	G	30	2	W0149	254R	24		23-31-13	050-099, 150-199
	G	30	2	W0149	255R	24		23-31-13	050-099, 150-199
	G	30	2	W0149	256R	24		23-31-13	050-099, 150-199
	H	31	2	W0139	122	24		23-51-12	275-299
	H	31	2	W0139	150	24		23-51-21	275-299
	H	31	2	W0139	174	24		23-51-41	275-299
	H	31	2	W0139	304Y	24		23-51-12	275-299
	G	31	2	W0149	207B	24		23-31-13	050-099, 150-199
	G	31	2	W0149	254B	24		23-31-13	050-099, 150-199
	G	31	2	W0149	255B	24		23-31-13	050-099, 150-199
	G	31	2	W0149	256B	24		23-31-13	050-099, 150-199
	G	32	2	W0149	533	24		23-31-13	050-099, 150-199
	G	32	2	W0149	534	24		23-31-13	050-099, 150-199
	G	32	2	W0149	565	24		23-31-13	050-099, 150-199
	G	33	2	W0149	538	24		23-31-13	050-099, 150-199
	G	33	2	W0149	539	24		23-31-13	051-099, 151-153
	G	33	2	W0149	567	24		23-31-13	050-099, 150-199
	H	34	2	W0139	124	24		23-51-12	275-299
	H	34	2	W0139	152	24		23-51-21	275-299
	H	34	2	W0139	176	24		23-51-41	275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 161

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	H	34	2	W0139	232R	24		23-51-12	275-299
	G	34	2	W0149	199	20		23-31-13	050-099, 150-199
	G	34	2	W0149	526	20		23-31-13	050-099, 150-199
	G	34	2	W0149	527	20		23-31-13	050-099, 150-199
	G	34	2	W0149	529	20		23-31-13	050-099, 150-199
	H	36	2	W0139	125	24		23-51-12	ALL
	H	36	2	W0139	155	24		23-51-21	ALL
	H	36	2	W0139	179	24		23-51-41	ALL
	H	36	2	W0139	305R	24		23-51-12	ALL
	H	38	2	W0139	126	24		23-51-12	ALL
	H	38	2	W0139	151	24		23-51-21	ALL
	H	38	2	W0139	175	24		23-51-41	ALL
	H	38	2	W0139	305Y	24		23-51-12	ALL
	G	4	2	W0139	226B	24		23-51-11	ALL
	G	4	2	W0149	236B	24		23-51-11	ALL
	G	40	2	W0139	001	16		23-12-11	162-199
	G	40	2	W0139	002	18		23-12-11	162-199
	G	40	2	W0149	001	16		23-12-11	162-199
	G	40	2	W0149	007	24		23-31-11	275-299
	G	40	2	W0149	177	24		23-31-11	275-299
	G	40	2	W0149	178	24		23-31-12	275-299
	H	41	2	W0139	128	24		23-51-12	ALL
	H	41	2	W0139	156	24		23-51-21	ALL
	H	41	2	W0139	180	24		23-51-41	ALL
	H	41	2	W0139	233R	24		23-51-12	ALL
	H	43	2	W0139	129	24		23-51-12	ALL
	H	43	2	W0139	153	24		23-51-21	ALL
	H	43	2	W0139	177	24		23-51-41	ALL
	H	43	2	W0139	234R	24		23-51-12	ALL
	H	45	2	W0139	130	24		23-51-13	ALL
	H	45	2	W0139	147	24		23-51-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 162

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	H	45	2	W0139	171	24		23-51-41	ALL
	H	45	2	W0139	255R	24		23-51-13	ALL
	H	48	2	W0139	131	24		23-51-13	ALL
	H	48	2	W0139	148	24		23-51-21	ALL
	H	48	2	W0139	172	24		23-51-41	ALL
	H	48	2	W0139	256R	24		23-51-13	ALL
	H	51	2	W0139	132	24		23-51-13	ALL
	H	51	2	W0139	149	24		23-51-21	ALL
	H	51	2	W0139	173	24		23-51-41	ALL
	H	51	2	W0139	254R	24		23-51-13	ALL
	H	53	2	W0139	133	24		23-51-13	ALL
	H	53	2	W0139	146	24		23-51-21	ALL
	H	53	2	W0139	170	24		23-51-41	ALL
	H	53	2	W0149	241R	24		23-51-13	ALL
	H	55	2	W0139	135	24		23-51-14	ALL
	H	55	2	W0139	160	24		23-51-21	ALL
	H	55	2	W0139	184	24		23-51-41	ALL
	H	55	2	W0149	305R	24		23-51-14	ALL
	H	57	2	W0139	043	24		23-51-14	ALL
	H	57	2	W0139	136	24		23-51-14	ALL
	H	57	2	W0139	161	24		23-51-21	ALL
	H	57	2	W0139	185	24		23-51-41	ALL
	H	57	2	W0149	135	24		23-11-21	ALL
	H	57	2	W0149	305Y	24		23-51-14	ALL
	H	59	2	W0139	137	24		23-51-14	ALL
	H	59	2	W0139	162	24		23-51-21	ALL
	H	59	2	W0139	186	24		23-51-41	ALL
	H	59	2	W0149	242R	24		23-51-14	ALL
	H	62	2	W0139	138	24		23-51-14	ALL
	H	62	2	W0139	163	24		23-51-21	ALL
	H	62	2	W0139	187	24		23-51-41	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 163

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	H	62	2	W0139	306R	24		23-51-14	ALL
	H	64	2	W0139	041	24		23-51-14	ALL
	H	64	2	W0139	139	24		23-51-14	ALL
	H	64	2	W0139	164	24		23-51-21	ALL
	H	64	2	W0139	188	24		23-51-41	ALL
	H	64	2	W0139	306Y	24		23-51-14	ALL
	H	64	2	W0139	778	24		23-11-11	ALL
	H	66	2	W0139	140	24		23-51-14	ALL
	H	66	2	W0139	165	24		23-51-21	ALL
	H	66	2	W0139	189	24		23-51-41	ALL
	H	66	2	W0139	236R	24		23-51-14	ALL
	G	68	2	W0149	779	24		23-34-13	150-199, 275-299
	G	68	2	W0149	783	24		23-34-13	150-199
	G	68	2	W0149	795	24		23-34-13	150-199, 275-299
	G	69	2	W0149	780	24		23-34-13	150-199, 275-299
	G	69	2	W0149	785	24		23-34-13	150-199
	G	69	2	W0149	796	24		23-34-13	150-199, 275-299
	H	7	2	W0139	665	24		23-51-11	275-299
	H	7	2	W0139	666	24		23-51-21	275-299
	H	7	2	W0139	667	24		23-51-41	275-299
	H	7	2	W0149	047	24		23-31-11	275-299
	H	7	2	W0149	303R	24		23-51-11	275-299
	H	71	2	W0139	228R	24		23-51-14	ALL
	H	71	2	W0139	240R	24		23-51-21	ALL
	H	71	2	W0139	246R	24		23-51-41	ALL
	H	71	2	W0139	302R	24		23-51-14	ALL
	H	73	2	W0139	037	24		23-51-14	ALL
	H	73	2	W0139	228B	24		23-51-14	ALL
	H	73	2	W0139	240B	24		23-51-21	ALL
	H	73	2	W0139	246B	24		23-51-41	ALL
	H	73	2	W0139	302Y	24		23-51-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 164

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	H	75	2	W0139	117	24		23-51-14	ALL
	H	75	2	W0139	144	24		23-51-21	ALL
	H	75	2	W0139	168	24		23-51-41	ALL
	H	75	2	W0139	230R	24		23-51-14	ALL
	H	77	2	W0139	577	24		23-22-12	050-099
	H	77	2	W0139	578	24		23-22-12	050-099
	Z	77	BJ	W0139	578	24		23-22-12	150-199, 275-299
	H	77	2	W0139	579	24		23-22-12	050-099
	Z	77	BJ	W0139	579	24		23-22-12	150-199, 275-299
	H	77	2	W0139	581	24		23-22-12	050-099
	Z	77	BJ	W0139	581	24		23-22-12	150-199, 275-299
	H	77	2	W0139	586	24		23-22-12	050-099
	H	77	2	W0139	617	24		23-22-12	050-099
	Z	77	BJ	W0139	617	24		23-22-12	150-199, 275-299
	H	77	2	W0139	754	24		23-22-12	050-099
	H	77	2	W0139	756	24		23-22-12	050-099
	Z	77	BJ	W0139	756	24		23-22-12	150-199, 275-299
	Z	77	BJ	W0139	876	24		23-22-12	150-199, 275-299
	Z	78	BJ	W0139	577	24		23-22-12	150-199, 275-299
	Z	78	BJ	W0139	586	24		23-22-12	150-199, 275-299
	Z	78	BJ	W0139	754	24		23-22-12	150-199, 275-299
	Z	78	BJ	W0139	876	24		23-22-12	150-199, 275-299
	H	79	2	W0139	229R	24		23-51-14	ALL
	H	79	2	W0139	241R	24		23-51-21	ALL
	H	79	2	W0139	247R	24		23-51-41	ALL
	H	79	2	W0139	303R	24		23-51-14	ALL
	H	81	2	W0139	035	24		23-51-14	ALL
	H	81	2	W0139	229B	24		23-51-14	ALL
	H	81	2	W0139	241B	24		23-51-21	ALL
	H	81	2	W0139	247B	24		23-51-41	ALL
	H	81	2	W0139	303Y	24		23-51-14	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 165

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	H	83	2	W0139	119	24		23-51-14	ALL
	H	83	2	W0139	145	24		23-51-21	ALL
	H	83	2	W0139	169	24		23-51-41	ALL
	H	83	2	W0139	231R	24		23-51-14	ALL
	H	85	2	W0139	217R	24		23-51-14	ALL
	H	85	2	W0139	218R	24		23-51-21	ALL
	H	85	2	W0139	235R	24		23-51-41	ALL
	H	85	2	W0139	307R	24		23-51-14	ALL
	H	87	2	W0139	039	24		23-51-14	ALL
	H	87	2	W0139	217B	24		23-51-14	ALL
	H	87	2	W0139	218B	24		23-51-21	ALL
	H	87	2	W0139	235B	24		23-51-41	ALL
	H	87	2	W0139	307Y	24		23-51-14	ALL
	H	89	2	W0139	069	24		23-51-21	ALL
	H	89	2	W0139	079	24		23-51-41	ALL
	H	89	2	W0139	108	24		23-51-14	ALL
	H	89	2	W0139	216R	24		23-51-14	ALL
	Z	9	BJ	W0139	552	24		23-51-11	150-152
	H	9	2	W0139	655	24		23-51-11	275-299
	H	9	2	W0139	659	24		23-51-11	275-299
	H	9	2	W0139	664	24		23-51-41	275-299
	Z	9	BJ	W0139	665	24		23-51-11	050-099, 153-199
	Z	9	BJ	W0139	666	24		23-51-21	050-099, 150-199
	Z	9	BJ	W0139	667	24		23-51-41	050-099, 150-199
	H	9	2	W0149	006	24		23-31-11	275-299
	Z	9	BJ	W0149	047	24		23-31-11	050-099, 150-199
	H	9	2	W0149	179	24		23-31-12	275-299
	Z	9	BJ	W0149	303R	24		23-51-11	050-099, 150-199
	H	9	2	W0149	303Y	24		23-51-11	275-299
	D	A001	2	W0149	519	24		23-31-11	050-099, 150-199
	D	A001	2	W0149	525	24		23-31-11	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 166

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	D	A002	2	W0149	519	24		23-31-11	050-099, 150-199
	D	A005	2	W0149	532	24		23-31-13	051-099, 151-153
	D	A005	2	W0149	553	24		23-31-14	050-099, 150-199
	D	A006	2	W0149	536	24		23-31-13	051-099, 151-153
	D	A007	2	W0149	536	24		23-31-13	051-099, 151-153
	D	A007	2	W0149	552	24		23-31-14	050-099, 150-199
	D	A008	2	W0149	540	24		23-31-13	051-099, 151-153
	F	A013	2	W0139	243R	24		23-51-41	ALL
	F	A013	2	W0149	122	24		23-51-41	ALL
	D	A015	2	W0149	532	24		23-31-13	051-099, 151-153
	D	A017	2	W0149	568	24		23-31-13	050-099, 150-199
	D	A019	2	W0149	045	24		23-34-13	050-099
	D	A020	2	W0149	157	24		23-34-13	050-099
	D	A025	2	W0149	546	24		23-31-13	050-099, 150-199
	D	A025	2	W0149	568	24		23-31-13	050-099, 150-199
	F	A033	2	W0139	280R	24		31-35-13	275-299
	F	A033	2	W0149	253R	24		31-35-13	275-299
	F	A035	2	W0139	280R	24		31-35-13	050-099, 150-199
	F	A035	2	W0149	253R	24		31-35-13	050-099, 150-199
	F	A070	2	W0139	786	24		23-34-12	ALL
	F	A070	2	W0149	776	24		23-34-12	ALL
	F	A091	2	W0139	788	24		23-34-12	ALL
	F	A091	2	W0149	778	24		23-34-12	ALL
	F	A103	2	W0139	094	24		23-31-13	ALL
	F	A103	2	W0149	019	24		23-31-13	ALL
	F	A105	2	W0139	215R	24		23-41-11	ALL
	F	A105	2	W0149	216R	24		23-41-11	ALL
	D	A109	2	W0149	763	24		23-34-13	150-199, 275-299
	D	A109	2	W0149	787	24		23-34-13	155
	D	A110	2	W0149	764	24		23-34-13	150-199, 275-299
	D	A110	2	W0149	786	24		23-34-13	155

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 167

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	D	A111	2	W0149	763	24		23-34-13	150-199, 275-299
	D	A111	2	W0149	781	24		23-34-13	150-199
	D	A111	2	W0149	783	24		23-34-13	275-299
	D	A112	2	W0149	764	24		23-34-13	150-199, 275-299
	D	A112	2	W0149	782	24		23-34-13	150-199
	D	A112	2	W0149	785	24		23-34-13	275-299
	D	A113	2	W0149	517	24		23-31-11	050-099, 150-199
	D	A114	2	W0149	510	24		23-31-11	050-099, 150-199
	D	A114	2	W0149	517	24		23-31-11	050-099, 150-199
	D	A115	2	W0149	540	24		23-31-13	051-099, 151-153
	D	A115	2	W0149	554	24		23-31-14	050-099, 150-199
	D	A116	2	W0149	570	24		23-31-13	050-099, 150-199
	F	A119	2	W0139	110	22		23-43-11	ALL
	F	A119	2	W0149	110	22		23-43-11	ALL
	F	A120	2	W0139	653	22		23-42-11	050-099, 162-199
	F	A120	2	W0149	616	22		23-42-11	050-099, 162-199
	D	A121	2	W0149	571	24		23-31-13	050-099, 150-199
	D	A124	2	W0149	106	20		23-43-11	ALL
	D	A124	2	W0149	109	20		23-43-11	ALL
	F	A135	2	W0139	098	22		23-42-11	ALL
	F	A135	2	W0149	089	22		23-42-11	ALL
	F	A136	2	W0139	100	22		23-42-11	ALL
	F	A136	2	W0149	091	22		23-42-11	ALL
	F	A137	2	W0139	102	22		23-42-11	ALL
	F	A137	2	W0149	093	22		23-42-11	ALL
	D	A138	2	W0149	545	24		23-31-13	050-099, 150-199
	D	A138	2	W0149	571	24		23-31-13	050-099, 150-199
	D	A139	2	W0149	544	24		23-31-13	050-099, 150-199
	D	A139	2	W0149	570	24		23-31-13	050-099, 150-199
	D	A140	2	W0149	018	24		23-31-12	050-099, 150-199
	D	A140	2	W0149	528	24		23-31-12	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 168

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	F	A141	2	W0139	725	22		23-71-11	ALL
	F	A141	2	W0149	125	22		23-71-11	ALL
	F	A142	2	W0139	401R	24		23-42-11	ALL
	F	A142	2	W0149	401R	24		23-42-11	ALL
	F	A143	2	W0139	401Y	24		23-42-11	ALL
	F	A143	2	W0149	401Y	24		23-42-11	ALL
	F	A144	2	W0139	773	24		23-32-12	ALL
	F	A144	2	W0149	028	24		23-32-12	ALL
	F	A149	2	W0139	271R	24		23-22-12	050-099, 150-199, 275-278
	F	A149	2	W0149	271R	24		23-22-12	050-099, 150-199, 275-278
	F	A150	2	W0139	272R	24		23-22-12	050-099, 150-199
	D	A150	2	W0149	144	24		23-31-12	275-299
	F	A150	2	W0149	272R	24		23-22-12	050-099, 150-199
	F	A151	2	W0139	271Z			23-22-12	050-099, 150-199, 275-278
	F	A151	2	W0149	271Z			23-22-12	050-099, 150-199, 275-278
	D	A152	2	W0139	655	24		23-51-11	ALL
	D	A152	2	W0149	9001	24		23-31-14	050-099, 150-199
	D	A152	2	W0149	9002	24		23-31-13	050-099, 150-199
	D	A153	2	W0139	659	24		23-51-11	ALL
	D	A154	2	W0139	664	24		23-51-41	050-099, 153-199, 275-299
	F	A156	2	W0139	651	22		23-42-11	050-099
	F	A156	2	W0149	614	22		23-42-11	050-099
	F	A157	2	W0139	272R	24		23-22-12	275-278
	D	A157	2	W0139	717	24		31-51-33	050-099, 162-199
	D	A157	2	W0149	072	24		31-51-33	050-099, 162-199
	F	A157	2	W0149	272R	24		23-22-12	275-278
	D	A158	2	W0149	786	24		23-34-13	150-199, 275-299
	D	A158	2	W0149	788	24		23-34-13	150-199
	F	A162	2	W0139	651	22		23-42-11	162-199
	F	A162	2	W0149	614	22		23-42-11	162-199
	D	A166	2	W0139	091	24		23-22-12	167-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 169

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	D	A168	2	W0139	026	24		23-21-11	050-099, 151, 275-276
	D	A168	2	W0139	159	24		23-21-11	150, 152-199, 277-299
	D	A168	2	W0139	785	24		23-21-11	ALL
	T	A172	2	W0139	035	24		23-51-14	ALL
	T	A173	2	W0139	037	24		23-51-14	ALL
	T	A174	2	W0139	039	24		23-51-14	ALL
	T	A175	2	W0139	041	24		23-51-14	ALL
	T	A176	2	W0139	043	24		23-51-14	ALL
	Y	A177	BJ	W0139	018	24		23-21-11	157, 167-199, 277-299
	Y	A177	BJ	W0139	051	24		23-12-11	157, 167-199, 277-299
	Y	A177	BJ	W0139	680	24		34-61-17	157, 167-199, 277-299
	Y	A177	BJ	W0139	782	24		31-31-17	157, 167-199, 277-299
	Y	A178	BJ	W0139	053	24		23-12-31	157, 167-199, 277-299
	Y	A178	BJ	W0139	054	24		23-21-11	157, 167-199, 277-299
	Y	A178	BJ	W0139	082	24		31-31-17	157, 167-199, 277-299
	Y	A178	BJ	W0139	682	24		34-61-17	157, 167-199, 277-299
	D	A179	2	W0139	674	24		34-61-17	157, 167-199, 277-299
	D	A179	2	W0139	675	24		34-61-17	157, 167-199, 277-299
	D	A180	2	W0139	675	24		34-61-17	157, 167-199, 277-299
	D	A180	2	W0139	676	24		34-61-17	157, 167-199, 277-299
	D	A181	2	W0139	676	24		34-61-17	157, 167-199, 277-299
	D	A181	2	W0139	677	24		34-61-17	157, 167-199, 277-299
	D	A182	2	W0139	677	24		34-61-17	157, 167-199, 277-299
	D	A182	2	W0139	678	24		34-61-17	157, 167-199, 277-299
	D	A183	2	W0139	678	24		34-61-17	157, 167-199, 277-299
	Y	A184	BJ	W0139	031	24		23-21-11	157, 167-199, 277-299
	Y	A184	BJ	W0139	684	24		34-61-17	157, 167-199, 277-299
	Y	A184	BJ	W0139	780	24		31-31-17	157, 167-199, 277-299
	Y	A184	BJ	W0149	076	24		23-11-21	157, 167-199, 277-299
	F	A185	2	W0139	205R	24		23-21-11	050-099, 150-156, 162-166, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 170

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	Y	A185	BJ	W0139	205R	24		23-21-11	157, 167-199, 277-299
	F	A185	2	W0149	201R	24		23-21-11	050-099, 150-156, 162-166, 275-276
	Y	A185	BJ	W0149	201R	24		23-21-11	157, 167-199, 277-299
	D	A186	2	W0149	709	24		23-34-13	275-299
	D	A186	2	W0149	786	24		23-34-13	150-154, 156-199, 275-299
	D	A186	2	W0149	803	24		23-34-13	150-199
	F	A187	2	W0149	791	24		23-34-13	150-199
	F	A187	2	W0149	806	24		23-34-13	150-199
	D	A188	2	W0149	710	24		23-34-13	275-299
	D	A188	2	W0149	787	24		23-34-13	150-154, 156-199
	D	A188	2	W0149	806	24		23-34-13	150-199
	F	A190	2	W0149	789	24		23-34-13	275-299
	F	A190	2	W0149	793	24		23-34-13	150-199
	F	A190	2	W0149	801	24		23-34-13	155
	F	A190	2	W0149	805	24		23-34-13	150-154, 156-199
	F	A196	2	W0139	626	22		23-24-11	050-099
	X	A196	BJ	W0139	626	22		23-24-11	150-199
	F	A196	2	W0149	195	22		23-24-11	050-099
	X	A196	BJ	W0149	195	22		23-24-11	150-199
	X	B196	BJ	W0139	627	22		23-24-11	150-199
	X	B196	BJ	W0149	196	22		23-24-11	150-199
	D	C001	2	W0149	521	24		23-31-11	050-099, 150-199
	D	C002	2	W0149	520	24		23-31-11	050-099, 150-199
	F	C003	2	W0139	226R	24		23-51-11	ALL
	F	C003	2	W0149	236R	24		23-51-11	ALL
	D	C005	2	W0149	533	24		23-31-13	051-099, 151-153
	D	C005	2	W0149	535	24		23-31-13	051-099, 151-153
	D	C005	2	W0149	905	24		23-31-13	050, 150, 154-199
	D	C006	2	W0149	535	24		23-31-13	051-099, 151-153
	D	C007	2	W0149	533	24		23-31-13	050, 150, 154-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 171

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	D	C007	2	W0149	537	24		23-31-13	051-099, 151-153
	D	C008	2	W0149	537	24		23-31-13	051-099, 151-153
	D	C008	2	W0149	539	24		23-31-13	051-099, 151-153
	F	C013	2	W0139	238R	24		23-51-21	ALL
	F	C013	2	W0149	243R	24		23-51-21	ALL
	D	C015	2	W0149	541	24		23-31-13	051-099, 151-153
	D	C015	2	W0149	542	24		23-31-13	051-099, 151-153
	D	C017	2	W0149	572	24		23-31-13	050-099, 150-199
	D	C019	2	W0149	154	24		23-34-13	050-099
	D	C019	2	W0149	155	24		23-34-13	050-099
	D	C020	2	W0149	155	24		23-34-13	050-099
	D	C025	2	W0149	565	24		23-31-13	050-099, 150-199
	F	C033	2	W0139	280B	24		31-35-13	275-299
	F	C033	2	W0149	253B	24		31-35-13	275-299
	F	C035	2	W0139	280B	24		31-35-13	050-099, 150-199
	F	C035	2	W0149	253B	24		31-35-13	050-099, 150-199
	F	C070	2	W0139	787	24		23-34-12	ALL
	F	C070	2	W0149	777	24		23-34-12	ALL
	F	C103	2	W0139	095	24		23-31-13	275-299
	F	C103	2	W0149	020	24		23-31-13	275-299
	F	C105	2	W0139	215B	24		23-41-11	ALL
	F	C105	2	W0149	216B	24		23-41-11	ALL
	D	C109	2	W0149	765	24		23-34-13	155, 275-299
	D	C109	#	W0149	784	24		23-34-13	150-199
	D	C109	2	W0149	784	24		23-34-13	275-299
	D	C110	2	W0149	766	24		23-34-13	155, 275-299
	D	C110	#	W0149	775	24		23-34-13	150-199
	D	C110	2	W0149	775	24		23-34-13	275-299
	D	C111	2	W0149	765	24		23-34-13	150-154, 156-199
	D	C111	2	W0149	768	24		23-34-13	150-199, 275-299
	D	C112	2	W0149	766	24		23-34-13	150-154, 156-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 172

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	D	C112	2	W0149	769	24		23-34-13	150-199, 275-299
	D	C113	2	W0149	513	24		23-31-11	050-099, 150-199
	D	C113	2	W0149	551	24		23-31-14	050-099, 150-199
	D	C114	2	W0149	515	24		23-31-11	050-099, 150-199
	D	C114	2	W0149	520	24		23-31-11	050-099, 150-199
	D	C115	2	W0149	541	24		23-31-13	051-099, 151-153
	D	C115	2	W0149	542	24		23-31-13	050, 150, 154-199
	D	C116	2	W0149	566	24		23-31-13	050-099, 150-199
	F	C119	2	W0139	111	22		23-43-11	ALL
	F	C119	2	W0149	111	22		23-43-11	ALL
	F	C120	2	W0139	716	22		23-42-11	ALL
	F	C120	2	W0149	071	22		23-42-11	ALL
	D	C121	2	W0149	567	24		23-31-13	050-099, 150-199
	D	C124	2	W0139	112	22		23-43-11	ALL
	D	C124	2	W0149	112	22		23-43-11	ALL
	F	C135	2	W0139	099	22		23-42-11	ALL
	F	C135	2	W0149	090	22		23-42-11	ALL
	F	C136	2	W0139	101	22		23-42-11	ALL
	F	C136	2	W0149	092	22		23-42-11	ALL
	F	C137	2	W0139	102Z			23-42-11	ALL
	F	C137	2	W0149	093Z			23-42-11	ALL
	D	C138	2	W0149	574	24		23-31-13	050-099, 150-199
	D	C139	2	W0149	573	24		23-31-13	050-099, 150-199
	F	C140	2	W0139	109	22		23-42-11	280-299
	F	C140	2	W0149	100	22		23-42-11	280-299
	D	C140	2	W0149	576	24		23-31-12	050-099, 150-199
	D	C140	2	W0149	808	24		23-31-12	050-099, 150-199
	F	C141	2	W0139	717	24		31-51-33	150-157, 275-299
	F	C141	2	W0149	072	24		31-51-33	150-157, 275-299
	F	C142	2	W0139	401B	24		23-42-11	ALL
	F	C142	2	W0149	401B	24		23-42-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 173

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	F	C143	2	W0139	401G	24		23-42-11	ALL
	F	C143	2	W0149	401G	24		23-42-11	ALL
	F	C144	2	W0139	401Z			23-42-11	ALL
	F	C144	2	W0149	401Z			23-42-11	ALL
	F	C145	2	W0139	774	22		23-34-11	ALL
	F	C145	2	W0149	039	22		23-34-11	ALL
	F	C149	2	W0139	271B	24		23-22-12	050-099, 150-199, 275-278
	F	C149	2	W0149	271B	24		23-22-12	050-099, 150-199, 275-278
	F	C150	2	W0139	272B	24		23-22-12	050-099, 150-199
	D	C150	2	W0149	142	24		23-31-12	275-299
	D	C150	2	W0149	143	24		23-31-12	275-299
	F	C150	2	W0149	272B	24		23-22-12	050-099, 150-199
	F	C151	2	W0139	272Z			23-22-12	050-099, 150-199
	F	C151	2	W0149	272Z			23-22-12	050-099, 150-199
	D	C152	2	W0139	554	24		23-51-11	ALL
	D	C152	2	W0149	9003	24		23-31-13	050-099, 150-199
	D	C153	2	W0139	660	24		23-51-11	ALL
	D	C154	2	W0139	551	24		23-51-41	ALL
	F	C156	2	W0139	272Z			23-22-12	275-278
	F	C156	2	W0139	652	22		23-42-11	050-099
	F	C156	2	W0149	272Z			23-22-12	275-278
	F	C156	2	W0149	615	22		23-42-11	050-099
	F	C157	2	W0139	272B	24		23-22-12	275-278
	F	C157	2	W0149	272B	24		23-22-12	275-278
	D	C157	2	W0149	613	24		23-42-11	050-099, 162-199
	D	C158	2	W0149	708	24		23-34-13	275-299
	D	C158	2	W0149	775	24		23-34-13	150-199, 275-299
	F	C162	2	W0139	652	22		23-42-11	162-199
	F	C162	2	W0149	615	22		23-42-11	162-199
	D	C166	2	W0139	637	24		23-22-12	167-199
	D	C168	2	W0139	692	24		23-22-11	277-278

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 174

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	D	C168	2	W0139	790	24		23-22-11	ALL
	D	C168	2	W0139	792	24		23-22-11	050-099, 151, 275-276, 280-299
	T	C172	2	W0139	036	20		23-51-14	ALL
	T	C173	2	W0139	038	20		23-51-14	ALL
	T	C174	2	W0139	040	20		23-51-14	ALL
	T	C175	2	W0139	042	20		23-51-14	ALL
	T	C176	2	W0139	044	20		23-51-14	ALL
	Y	C177	BJ	W0139	019	24		23-21-11	157, 167-199, 277-299
	Y	C177	BJ	W0139	052	24		23-12-21	157, 167-199, 277-299
	Y	C177	BJ	W0139	681	24		34-61-17	157, 167-199, 277-299
	Y	C177	BJ	W0139	781	24		31-31-17	157, 167-199, 277-299
	Y	C178	BJ	W0139	030	24		23-21-11	157, 167-199, 277-299
	Y	C178	BJ	W0139	683	24		34-61-17	157, 167-199, 277-299
	Y	C178	BJ	W0139	772	24		23-11-11	157, 167-199, 277-299
	Y	C178	BJ	W0139	779	24		31-31-17	157, 167-199, 277-299
	D	C179	2	W0139	680	24		34-61-17	157, 167-199, 277-299
	D	C180	2	W0139	681	24		34-61-17	157, 167-199, 277-299
	D	C181	2	W0139	682	24		34-61-17	157, 167-199, 277-299
	D	C182	2	W0139	683	24		34-61-17	157, 167-199, 277-299
	D	C183	2	W0139	684	24		34-61-17	157, 167-199, 277-299
	Y	C184	BJ	W0139	752	24		23-12-21	157, 167-199, 277-299
	Y	C184	BJ	W0139	753	24		23-12-31	157, 167-199, 277-299
	Y	C184	BJ	W0149	051	24		23-12-21	157, 167-199, 277-299
	F	C185	2	W0139	205B	24		23-21-11	050-099, 150-156, 162-166, 275-276
	Y	C185	BJ	W0139	205B	24		23-21-11	157, 167-199, 277-299
	F	C185	2	W0149	201B	24		23-21-11	050-099, 150-156, 162-166, 275-276
	Y	C185	BJ	W0149	201B	24		23-21-11	157, 167-199, 277-299
	D	C186	2	W0149	800	24		23-34-13	150-199, 275-299
	F	C187	2	W0149	792	24		23-34-13	150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 175

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	F	C187	2	W0149	803	24		23-34-13	150-199
	D	C188	2	W0149	706	24		23-34-13	275-299
	D	C188	2	W0149	784	24		23-34-13	150-199, 275-299
	D	C188	2	W0149	799	24		23-34-13	150-199
	F	C190	2	W0149	790	24		23-34-13	275-299
	F	C190	2	W0149	794	24		23-34-13	150-199
	F	C190	2	W0149	802	24		23-34-13	155
	F	C190	2	W0149	804	24		23-34-13	150-154, 156-199
	F	C196	2	W0139	627	22		23-24-11	050-099
	F	C196	2	W0149	196	22		23-24-11	050-099
	G	CAP	Y	W0149	273R	22		23-22-12	050-099, 150-199, 275-278
	Z	CAP	Y	W0149	558	20		23-31-14	050-099
	G	DED		W0139	058Z			23-22-11	150, 152-199, 277-299
	G	DED		W0139	097Z			23-34-11	ALL
	G	DED		W0139	553Z			23-22-11	277-299
	H	DED		W0139	650Z			23-42-11	050-099
	Z	DED		W0139	650Z			23-42-11	162-199
	G	DED		W0139	689Z			23-22-12	275-299
	F	DED		W0139	774Z			23-34-11	ALL
	G	DED		W0139	775Z			23-34-11	ALL
	G	DED		W0139	901Z			23-22-11	150, 152-199
	G	DED		W0139	902Z			23-22-12	150, 152-199
	H	DED		W0149	003Z			23-31-11	050-099, 150-199
	G	DED		W0149	003Z			23-31-11	275-299
	H	DED		W0149	004Z			23-31-11	050-099, 150-199
	G	DED		W0149	004Z			23-31-11	275-299
	H	DED		W0149	005Z			23-31-11	050-099, 150-199
	G	DED		W0149	005Z			23-31-11	275-299
	G	DED		W0149	038Z			23-34-11	ALL
	F	DED		W0149	039Z			23-34-11	ALL
	G	DED		W0149	040Z			23-34-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 176

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0139		284T0116-1 (continued)					SHELF/E02/05		ALL
TB0139	D	DIODEBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	F	BACM15C1A (continued)					SHELF/E02/05		ALL
TB0139	G	BACM15C1B (continued)					SHELF/E02/05		ALL
TB0139	H	BACM15C2A (continued)					SHELF/E02/05		ALL
TB0139	T	RCNETWORKBLOCK-REF284T0125- (continued)					SHELF/E02/05		ALL
TB0139	X	BACM15C3A (continued)					SHELF/E02/05		ALL
TB0139	Y	BACM15C3B (continued)					SHELF/E02/05		ALL
TB0139	Z	BACM15C3C (continued)					SHELF/E02/05		ALL
	G	DED		W0149	057Z			23-42-12	150-157, 275-299
	Z	DED		W0149	057Z			23-42-12	162-199
	H	DED		W0149	087Z			23-42-11	050-099
	G	DED		W0149	087Z			23-42-11	150-157, 275-299
	Z	DED		W0149	087Z			23-42-11	162-199
	H	DED		W0149	104Z			23-42-11	050-099
	G	DED		W0149	104Z			23-42-11	150-157, 275-299
	Z	DED		W0149	104Z			23-42-11	162-199
	G	DED		W0149	141Z			23-31-12	275-299
	H	DED		W0149	197Z			23-31-11	050-099, 150-199
	G	DED		W0149	199Z			23-31-13	050-099, 150-199
	H	DED		W0149	199Z			23-31-13	050-099, 150-199
	H	DED		W0149	522Z			23-31-11	050-099, 150-199
	G	DED		W0149	526Z			23-31-13	050-099, 150-199
	G	DED		W0149	527Z			23-31-13	050-099, 150-199
	G	DED		W0149	529Z			23-31-13	050-099, 150-199
	Z	DED		W0149	555Z			23-31-14	050-099, 150-199
	Z	DED		W0149	556Z			23-31-14	050-099, 150-199
	Z	DED		W0149	557Z			23-31-14	050-099, 150-199
	Z	DED		W0149	558Z			23-31-14	050-099, 150-199
	Z	DED		W0149	559Z			23-31-14	050-099, 150-199
	H	DED		W0149	560Z			23-31-14	050-099, 150-199
	Z	DED		W0149	560Z			23-31-14	050-099, 150-199
	H	DED		W0149	622Z			23-42-11	050-099
	Z	DED		W0149	622Z			23-42-11	162-199
	H	DED		W0149	623Z			23-42-11	050-099
	Z	DED		W0149	623Z			23-42-11	162-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 177

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		284T0384					SHELF/E02/01		ALL
TB0141	F	BACM15C1A					SHELF/E02/01		ALL
TB0141	G	BACM15C1B					SHELF/E02/01		ALL
TB0141	H	BACM15C2A					SHELF/E02/01		ALL
TB0141	Z	BACM15C3B					SHELF/E02/01		150-199, 275-299
	G			W0131	205Z			22-21-21	ALL
	G			W0131	206Z			27-11-22	ALL
	G			W0131	207Z			27-11-22	ALL
	G			W0141	205Z			22-21-21	ALL
	G			W0141	206Z			27-11-22	ALL
	G			W0141	207Z			27-11-22	ALL
	Z			W0141	284Z			22-21-31	150-199, 275-299
	Z			W0141	285Z			22-21-31	150-199, 275-299
	Z			W0141	286Z			22-21-31	150-199, 275-299
	H	1	2	W0131	203R	22		22-21-21	ALL
	H	1	2	W0131	204R	22		22-21-21	ALL
	H	1	2	W0131	222R	22		27-21-22	ALL
	H	1	2	W0131	223R	22		27-21-22	ALL
	H	1	2	W0131	224R	22		27-21-22	ALL
	H	1	2	W0131	225R	22		27-21-22	ALL
	G	10	2	W0131	303B	22		27-61-13	ALL
	G	10	2	W0131	306B	22		27-61-17	ALL
	G	10	2	W0131	307B	22		27-61-17	ALL
	G	10	2	W0131	310B	22		27-61-18	ALL
	H	101	2	W0131	052	22		27-09-12	ALL
	H	101	2	W0131	053	22		27-09-12	ALL
	H	101	2	W0131	054	22		27-09-12	ALL
	H	101	2	W0131	055	22		27-09-12	ALL
	H	101	2	W0131	056	22		27-09-12	ALL
	H	101	2	W0131	057	22		27-09-12	ALL
	H	101	2	W0131	058	22		27-09-12	ALL
	G	103	2	W0131	226R	22		27-21-22	ALL
	G	103	2	W0131	227R	22		27-21-22	ALL
	G	103	2	W0131	228R	22		27-21-22	ALL
	G	104	2	W0131	226B	22		27-21-22	ALL
	G	104	2	W0131	227B	22		27-21-22	ALL
	G	104	2	W0131	228B	22		27-21-22	ALL
	G	105	2	W0131	312R	22		27-21-22	ALL
	G	105	2	W0131	313R	22		27-21-22	ALL
	G	105	2	W0131	314R	22		27-21-22	ALL
	G	106	2	W0131	312B	22		27-21-22	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 178

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		<b>284T0384 (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>Z</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/01</b>		<b>150-199, 275-299</b>
	G	106	2	W0131	313B	22		27-21-22	ALL
	G	106	2	W0131	314B	22		27-21-22	ALL
	G	107	2	W0131	312Y	22		27-21-22	ALL
	G	107	2	W0131	313Y	22		27-21-22	ALL
	G	107	2	W0131	314Y	22		27-21-22	ALL
	G	108	2	W0131	210R	22		27-61-13	ALL
	G	108	2	W0131	211R	22		27-61-13	ALL
	G	108	2	W0131	213R	22		27-61-13	ALL
	G	109	2	W0131	210B	22		27-61-13	ALL
	G	109	2	W0131	211B	22		27-61-13	ALL
	G	109	2	W0131	213B	22		27-61-13	ALL
	G	11	2	W0131	303Y	22		27-61-13	ALL
	G	11	2	W0131	306Y	22		27-61-17	ALL
	G	11	2	W0131	307Y	22		27-61-17	ALL
	G	11	2	W0131	310Y	22		27-61-18	ALL
	H	110	2	W0131	208R	22		27-61-13	ALL
	H	110	2	W0131	214R	22		27-61-17	ALL
	H	110	2	W0131	215R	22		27-61-17	ALL
	H	110	2	W0131	216R	22		27-61-17	ALL
	H	110	2	W0131	217R	22		27-61-17	ALL
	H	110	2	W0131	218R	22		27-61-18	ALL
	H	112	2	W0131	137	22		27-61-17	ALL
	H	112	2	W0131	208B	22		27-61-13	ALL
	H	112	2	W0131	214B	22		27-61-17	ALL
	H	112	2	W0131	215B	22		27-61-17	ALL
	H	112	2	W0131	216B	22		27-61-17	ALL
	H	112	2	W0131	217B	22		27-61-17	ALL
	H	112	2	W0131	218B	22		27-61-18	ALL
	G	12	2	W0131	302R	22		27-61-13	ALL
	G	12	2	W0131	308R	22		27-61-17	ALL
	G	12	2	W0131	309R	22		27-61-17	ALL
	G	12	2	W0131	311R	22		27-61-18	ALL
	G	129	2	W0151	028	22		27-09-13	ALL
	G	129	2	W0151	030	22		27-09-13	ALL
	G	129	2	W0151	032	22		27-09-13	ALL
	G	13	2	W0131	302B	22		27-61-13	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 179

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		<b>284T0384 (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>Z</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/01</b>		<b>150-199, 275-299</b>
	G	13	2	W0131	308B	22		27-61-17	ALL
	G	13	2	W0131	309B	22		27-61-17	ALL
	G	13	2	W0131	311B	22		27-61-18	ALL
	G	130	2	W0151	029	22		27-09-13	ALL
	G	130	2	W0151	031	22		27-09-13	ALL
	G	130	2	W0151	033	22		27-09-13	ALL
	H	131	2	W0151	203R	22		27-61-13	ALL
	H	131	2	W0151	207R	22		27-61-17	ALL
	H	131	2	W0151	210R	22		27-61-18	ALL
	H	131	2	W0151	211R	22		27-61-18	ALL
	H	131	2	W0151	212R	22		27-61-18	ALL
	H	131	2	W0151	213R	22		27-61-18	ALL
	H	133	2	W0151	085	22		27-61-18	ALL
	H	133	2	W0151	203B	22		27-61-13	ALL
	H	133	2	W0151	207B	22		27-61-17	ALL
	H	133	2	W0151	210B	22		27-61-18	ALL
	H	133	2	W0151	211B	22		27-61-18	ALL
	H	133	2	W0151	212B	22		27-61-18	ALL
	H	133	2	W0151	213B	22		27-61-18	ALL
	G	135	2	W0151	205R	22		27-61-17	ALL
	G	135	2	W0151	208R	22		27-61-17	ALL
	G	135	2	W0151	209R	22		27-61-17	ALL
	G	136	2	W0151	205B	22		27-61-17	ALL
	G	136	2	W0151	208B	22		27-61-17	ALL
	G	136	2	W0151	209B	22		27-61-17	ALL
	G	14	2	W0131	302Y	22		27-61-13	ALL
	G	14	2	W0131	308Y	22		27-61-17	ALL
	G	14	2	W0131	309Y	22		27-61-17	ALL
	G	14	2	W0131	311Y	22		27-61-18	ALL
	H	147	2	W1131	020	22		27-09-14	ALL
	H	147	2	W1131	021	22		27-09-14	ALL
	H	147	2	W1131	022	22		27-09-14	ALL
	H	147	2	W1131	023	22		27-09-14	ALL
	G	149	2	W1131	015	22		27-09-14	ALL
	G	149	2	W1131	016	22		27-09-14	ALL
	G	149	2	W1131	024	22		27-09-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 180

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		284T0384 (continued)					SHELF/E02/01		ALL
TB0141	F	BACM15C1A (continued)					SHELF/E02/01		ALL
TB0141	G	BACM15C1B (continued)					SHELF/E02/01		ALL
TB0141	H	BACM15C2A (continued)					SHELF/E02/01		ALL
TB0141	Z	BACM15C3B (continued)					SHELF/E02/01		150-199, 275-299
	H	15	2	W0131	016	22		27-09-11	ALL
	H	15	2	W0131	017	22		27-09-11	ALL
	H	15	2	W0131	018	22		27-09-11	ALL
	H	15	2	W0131	100	22		22-21-21	ALL
	H	15	2	W0131	107	22		27-61-13	ALL
	H	15	2	W0131	111	22		27-61-17	ALL
	H	15	2	W0131	127	22		27-61-18	ALL
	G	150	2	W1131	046	22		27-61-12	ALL
	G	150	2	W1131	047	22		27-61-12	ALL
	G	150	2	W1131	048	22		27-61-12	ALL
	G	150	2	W1131	049	22		27-61-12	ALL
	G	174	2	W0141	215R	22		27-61-18	ALL
	G	174	2	W0141	216R	22		27-61-18	ALL
	G	174	2	W0141	217R	22		27-61-18	ALL
	G	175	2	W0141	215B	22		27-61-18	ALL
	G	175	2	W0141	216B	22		27-61-18	ALL
	G	175	2	W0141	217B	22		27-61-18	ALL
	G	176	2	W0141	160	22		27-61-18	ALL
	G	176	2	W0141	218B	22		27-61-18	ALL
	G	176	2	W0141	223B	22		27-61-18	ALL
	G	177	2	W0141	159	22		27-61-18	ALL
	G	177	2	W0141	219B	22		27-61-18	ALL
	G	177	2	W0141	224B	22		27-61-18	ALL
	H	178	2	W0141	210R	22		27-61-13	ALL
	H	178	2	W0141	211R	22		27-61-13	ALL
	H	178	2	W0141	212R	22		27-61-13	ALL
	H	178	2	W0141	213R	22		27-61-13	ALL
	H	178	2	W0141	214R	22		27-61-17	ALL
	H	178	2	W0141	220R	22		27-61-18	ALL
	H	180	2	W0141	128	22		27-61-13	ALL
	H	180	2	W0141	210B	22		27-61-13	ALL
	H	180	2	W0141	211B	22		27-61-13	ALL
	H	180	2	W0141	212B	22		27-61-13	ALL
	H	180	2	W0141	213B	22		27-61-13	ALL
	H	180	2	W0141	214B	22		27-61-17	ALL
	H	180	2	W0141	220B	22		27-61-18	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 181

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		<b>284T0384 (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>Z</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/01</b>		<b>150-199, 275-299</b>
	H	182	2	W0141	074	22		27-09-13	ALL
	H	182	2	W0141	075	22		27-09-13	ALL
	H	182	2	W0141	076	22		27-09-13	ALL
	H	182	2	W0141	077	22		27-09-13	ALL
	H	182	2	W0141	078	22		27-09-13	ALL
	H	182	2	W0141	079	22		27-09-13	ALL
	H	182	2	W0141	080	22		27-09-13	ALL
	H	184	2	W0141	081	22		27-09-13	ALL
	H	184	2	W0141	082	22		27-09-13	ALL
	H	184	2	W0141	083	22		27-09-13	280-299
	H	184	2	W0141	084	22		27-09-13	ALL
	H	184	2	W0141	085	22		27-09-13	ALL
	H	184	2	W0141	086	22		27-09-13	ALL
	H	184	2	W0141	087	22		27-09-13	ALL
	H	186	2	W0141	066	22		27-09-12	ALL
	H	186	2	W0141	067	22		27-09-12	ALL
	H	186	2	W0141	068	22		27-09-12	ALL
	H	186	2	W0141	069	22		27-09-12	ALL
	H	186	2	W0141	070	22		27-09-12	ALL
	H	186	2	W0141	071	22		27-09-12	ALL
	H	186	2	W0141	072	22		27-09-12	ALL
	H	186	2	W0141	073	22		27-09-12	ALL
	G	188	2	W0141	205R	24		22-21-21	ALL
	G	188	2	W0141	206R	24		27-11-22	ALL
	G	188	2	W0141	207R	24		27-11-22	ALL
	G	189	2	W0141	205B	24		22-21-21	ALL
	G	189	2	W0141	206B	24		27-11-22	ALL
	G	189	2	W0141	207B	24		27-11-22	ALL
	H	190	2	W0141	011	22		22-21-21	ALL
	H	190	2	W0141	050	22		27-09-11	ALL
	H	190	2	W0141	051	22		27-09-11	ALL
	H	190	2	W0141	052	22		27-09-11	ALL
	H	190	2	W0141	129	22		27-61-13	ALL
	H	190	2	W0141	139	22		27-61-17	ALL
	H	190	2	W0141	167	22		27-61-18	ALL
	H	29	2	W0151	022	22		27-09-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 182

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		<b>284T0384 (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	F	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	G	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	H	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	Z	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/01</b>		<b>150-199, 275-299</b>
	H	29	2	W0151	023	22		27-09-12	ALL
	H	29	2	W0151	024	22		27-09-12	ALL
	H	29	2	W0151	025	22		27-09-12	ALL
	H	29	2	W0151	026	22		27-09-12	ALL
	H	29	2	W0151	027	22		27-09-12	ALL
	H	3	2	W0131	130	22		27-21-22	ALL
	H	3	2	W0131	203B	22		22-21-21	ALL
	H	3	2	W0131	204B	22		22-21-21	ALL
	H	3	2	W0131	222B	22		27-21-22	ALL
	H	3	2	W0131	223B	22		27-21-22	ALL
	H	3	2	W0131	224B	22		27-21-22	ALL
	H	3	2	W0131	225B	22		27-21-22	ALL
	G	31	2	W0151	044	22		27-61-11	ALL
	G	31	2	W0151	045	22		27-61-11	ALL
	G	31	2	W0151	046	22		27-61-11	ALL
	G	31	2	W0151	047	22		27-61-11	ALL
	G	32	2	W0151	301R	22		27-61-13	ALL
	G	32	2	W0151	303R	22		27-61-17	ALL
	G	32	2	W0151	307R	22		27-61-18	ALL
	G	32	2	W0151	309R	22		27-61-18	ALL
	G	33	2	W0151	301B	22		27-61-13	ALL
	G	33	2	W0151	303B	22		27-61-17	ALL
	G	33	2	W0151	307B	22		27-61-18	ALL
	G	33	2	W0151	309B	22		27-61-18	ALL
	G	34	2	W0151	301Y	22		27-61-13	ALL
	G	34	2	W0151	303Y	22		27-61-17	ALL
	G	34	2	W0151	307Y	22		27-61-18	ALL
	G	34	2	W0151	309Y	22		27-61-18	ALL
	G	35	2	W0151	302R	22		27-61-13	ALL
	G	35	2	W0151	304R	22		27-61-17	ALL
	G	35	2	W0151	308R	22		27-61-18	ALL
	G	35	2	W0151	310R	22		27-61-18	ALL
	G	36	2	W0151	302B	22		27-61-13	ALL
	G	36	2	W0151	304B	22		27-61-17	ALL
	G	36	2	W0151	308B	22		27-61-18	ALL
	G	36	2	W0151	310B	22		27-61-18	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 183

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		<b>284T0384 (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>Z</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/01</b>		<b>150-199, 275-299</b>
	G	37	2	W0151	302Y	22		27-61-13	ALL
	G	37	2	W0151	304Y	22		27-61-17	ALL
	G	37	2	W0151	308Y	22		27-61-18	ALL
	G	37	2	W0151	310Y	22		27-61-18	ALL
	G	49	2	W1131	025	22		27-11-22	ALL
	G	49	2	W1131	026	22		27-11-22	ALL
	G	49	2	W1131	027	20		27-11-22	ALL
	G	5	2	W0131	205R	24		22-21-21	ALL
	G	5	2	W0131	206R	24		27-11-22	ALL
	G	5	2	W0131	207R	24		27-11-22	ALL
	G	50	2	W1131	028	22		27-11-22	ALL
	G	50	2	W1131	029	20		27-11-22	ALL
	G	50	2	W1131	030	20		27-11-22	ALL
	G	51	2	W1131	031	22		27-11-22	ALL
	G	51	2	W1131	032	20		27-11-22	ALL
	G	51	2	W1131	033	20		27-11-22	ALL
	G	52	2	W1131	034	22		27-11-22	ALL
	G	52	2	W1131	035	22		27-11-22	ALL
	G	52	2	W1131	036	22		27-11-22	ALL
	G	53	2	W1131	037	22		27-11-22	ALL
	G	53	2	W1131	038	22		27-11-22	ALL
	G	53	2	W1131	039	22		27-11-22	ALL
	Z	54	BJ	W0141	284R	24		22-21-31	150-199, 275-299
	Z	54	BJ	W0141	285R	24		22-21-31	150-199, 275-299
	Z	54	BJ	W0141	286R	24		22-21-31	150-199, 275-299
	Z	55	BJ	W0141	284B	24		22-21-31	150-199, 275-299
	Z	55	BJ	W0141	285B	24		22-21-31	150-199, 275-299
	Z	55	BJ	W0141	286B	24		22-21-31	150-199, 275-299
	G	6	2	W0131	205B	24		22-21-21	ALL
	G	6	2	W0131	206B	24		27-11-22	ALL
	G	6	2	W0131	207B	24		27-11-22	ALL
	G	7	2	W0131	076	22		27-41-21	ALL
	G	7	2	W0131	077	22		27-41-21	ALL
	G	7	2	W0131	078	22		27-41-21	ALL
	G	73	2	W0141	303R	22		27-61-13	ALL
	G	73	2	W0141	304R	22		27-61-13	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 184

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		<b>284T0384 (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>Z</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/01</b>		<b>150-199, 275-299</b>
G		73	2	W0141	305R	22		27-61-17	ALL
G		73	2	W0141	307R	22		27-61-18	ALL
G		74	2	W0141	303B	22		27-61-13	ALL
G		74	2	W0141	304B	22		27-61-13	ALL
G		74	2	W0141	305B	22		27-61-17	ALL
G		74	2	W0141	307B	22		27-61-18	ALL
G		75	2	W0141	303Y	22		27-61-13	ALL
G		75	2	W0141	304Y	22		27-61-13	ALL
G		75	2	W0141	305Y	22		27-61-17	ALL
G		75	2	W0141	307Y	22		27-61-18	ALL
G		76	2	W0141	301R	22		27-61-13	ALL
G		76	2	W0141	302R	22		27-61-13	ALL
G		76	2	W0141	306R	22		27-61-17	ALL
G		76	2	W0141	308R	22		27-61-18	ALL
G		77	2	W0141	301B	22		27-61-13	ALL
G		77	2	W0141	302B	22		27-61-13	ALL
G		77	2	W0141	306B	22		27-61-17	ALL
G		77	2	W0141	308B	22		27-61-18	ALL
G		78	2	W0141	301Y	22		27-61-13	ALL
G		78	2	W0141	302Y	22		27-61-13	ALL
G		78	2	W0141	306Y	22		27-61-17	ALL
G		78	2	W0141	308Y	22		27-61-18	ALL
H		79	2	W0141	120	22		27-61-12	ALL
H		79	2	W0141	121	22		27-61-12	ALL
H		79	2	W0141	122	22		27-61-12	ALL
H		79	2	W0141	123	22		27-61-12	ALL
H		79	2	W0141	124	22		27-61-12	ALL
G		8	2	W0131	092	22		27-61-11	ALL
G		8	2	W0131	093	22		27-61-11	ALL
G		8	2	W0131	094	22		27-61-11	ALL
G		8	2	W0131	095	22		27-61-11	ALL
H		81	2	W0141	115	22		27-61-11	ALL
H		81	2	W0141	116	22		27-61-11	ALL
H		81	2	W0141	117	22		27-61-11	ALL
H		81	2	W0141	118	22		27-61-11	ALL
H		81	2	W0141	119	22		27-61-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 185

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0141		<b>284T0384 (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/01</b>		<b>ALL</b>
TB0141	<b>Z</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/01</b>		<b>150-199, 275-299</b>
	G	83	2	W0141	103	22		27-41-21	ALL
	G	83	2	W0141	104	22		27-41-21	ALL
	G	83	2	W0141	105	22		27-41-21	ALL
	G	83	2	W0141	605	22		27-41-21	ALL
	G	84	2	W0141	089	22		27-09-14	ALL
	G	84	2	W0141	090	22		27-09-14	ALL
	G	84	2	W0141	098	22		27-09-14	ALL
	H	85	2	W0141	094	22		27-09-14	ALL
	H	85	2	W0141	095	22		27-09-14	ALL
	H	85	2	W0141	096	22		27-09-14	ALL
	H	85	2	W0141	097	22		27-09-14	ALL
	G	87	2	W0141	028	22		22-24-21	ALL
	G	87	2	W0141	029	22		22-24-21	ALL
	G	87	2	W0141	030	22		22-24-21	ALL
	G	9	2	W0131	303R	22		27-61-13	ALL
	G	9	2	W0131	306R	22		27-61-17	ALL
	G	9	2	W0131	307R	22		27-61-17	ALL
	G	9	2	W0131	310R	22		27-61-18	ALL
	G	90	2	W0141	012	22		22-21-21	ALL
	G	90	2	W0141	013	22		22-21-21	ALL
	G	90	2	W0141	014	22		22-21-21	ALL
	G	91	2	W0141	006	22		22-21-21	ALL
	G	91	2	W0141	007	22		22-21-21	ALL
	G	91	2	W0141	008	22		22-21-21	ALL
	G	91	2	W0141	009	22		22-21-21	ALL
	F	A173	2	W0141	218R	22		27-61-18	ALL
	F	A173	2	W0141	223R	22		27-61-18	ALL
	F	C173	2	W0141	219R	22		27-61-18	ALL
	F	C173	2	W0141	224R	22		27-61-18	ALL
	G	DED		W1131	025Z			27-11-22	ALL
	G	DED		W1131	026Z			27-11-22	ALL
	G	DED		W1131	027Z			27-11-22	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 186

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK					SHELF/E02/03		ALL
TB0145	F	BACM15C1A					SHELF/E02/03		ALL
TB0145	G	BACM15C1B					SHELF/E02/03		ALL
TB0145	H	BACM15C2A					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK					SHELF/E02/03		ALL
TB0145	X	BACM15C3A					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C					SHELF/E02/03		ALL
	G	103	2	W0145	651	24		34-53-22	150-154
	G	103	2	W0145	667	24		34-53-22	150-154
	G	103	2	W0145	668	24		34-53-22	150-154
	Z	125	BJ	W0135	525R	24		31-31-20	277-299
	Z	125	BJ	W0145	281R	24		34-55-21	277-299
	Z	125	BJ	W0145	284R	24		34-22-29	277-299
	Z	125	BJ	W0145	554R	24		31-35-12	277-299
	Z	125	BJ	W0145	715R	24		34-61-27	277-299
	Z	126	BJ	W0135	525B	24		31-31-20	277-299
	Z	126	BJ	W0145	281B	24		34-55-21	277-299
	Z	126	BJ	W0145	284B	24		34-22-29	277-299
	Z	126	BJ	W0145	554B	24		31-35-12	277-299
	Z	126	BJ	W0145	715B	24		34-61-27	277-299
	Z	131	BJ	W0135	052	22		31-31-18	ALL
	Z	131	BJ	W0135	099	22		31-31-11	ALL
	Z	131	BJ	W0135	700	20		31-31-11	ALL
	Z	131	BJ	W0135	783	24		31-31-21	ALL
	Z	131	BJ	W0145	105	24		31-31-12	ALL
	Z	131	BJ	W0145	117	24		31-31-11	ALL
	Z	131	BJ	W0145	158	24		31-31-12	ALL
	Z	131	BJ	W0145	179	22		31-31-18	ALL
	Z	132	BJ	W0135	022	22		31-31-11	ALL
	Z	132	BJ	W0135	074	22		31-31-11	ALL
	Z	132	BJ	W0135	075	22		31-31-11	ALL
	Z	132	BJ	W0135	100	22		31-31-11	ALL
	Z	132	BJ	W0145	106	22		31-31-11	ALL
	Z	137	BJ	W0135	784	22		31-31-25	050-099, 150-199
	Z	137	BJ	W0135	785	22		31-31-25	050-099, 150-199
	Z	137	BJ	W0135	786	22		31-31-25	050-099, 150-199
	Z	137	BJ	W0135	787	22		31-31-25	050-099, 150-199
	Z	137	BJ	W0135	788	22		31-31-25	050-099, 150-199
	Z	137	BJ	W0135	799	22		31-31-25	050-099, 150-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 187

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Z	138	BJ	W0135	012	24		31-31-13	ALL
	Z	138	BJ	W0135	073	22		31-31-11	ALL
	Z	138	BJ	W0135	116	22		31-31-15	ALL
	Z	138	BJ	W0135	700	20		31-31-11	ALL
	Z	138	BJ	W0135	750	24		31-31-22	ALL
	Z	138	BJ	W0135	892	24		31-31-17	ALL
	Z	138	BJ	W0145	196	24		31-31-19	ALL
	Z	15	BJ	W0135	296R	24		34-61-15	050-099, 150-199, 275-276
	Z	15	BJ	W0145	204R	24		27-32-21	051-099, 151, 275-276
	Z	15	BJ	W0145	234R	24		34-61-25	050-099, 150-199, 275-276
	Z	15	BJ	W0145	266R	24		31-35-13	050-099, 150-199, 275-276
	Z	15	BJ	W0145	526R	24		34-21-21	050-099, 150-199, 275-276
	Z	15	BJ	W0145	557R	24		34-61-26	050-099, 150-199, 275-276
	Z	153	BJ	W0135	188	22		31-31-22	ALL
	Z	153	BJ	W0135	662	22		31-31-15	ALL
	Z	153	BJ	W0135	665	22		31-31-15	ALL
	Z	153	BJ	W0135	667	22		31-31-15	ALL
	Z	153	BJ	W0135	671	22		31-31-15	ALL
	Z	153	BJ	W0135	772	22		31-31-22	ALL
	Z	153	BJ	W0135	789	22		31-31-25	050-099, 150-199
	Z	153	BJ	W0135	799	22		31-31-25	050-099, 150-199
	Z	16	BJ	W0135	296B	24		34-61-15	050-099, 150-199, 275-276
	Z	16	BJ	W0145	204B	24		27-32-21	051-099, 151, 275-276
	Z	16	BJ	W0145	234B	24		34-61-25	050-099, 150-199, 275-276
	Z	16	BJ	W0145	266B	24		31-35-13	050-099, 150-199, 275-276
	Z	16	BJ	W0145	526B	24		34-21-21	050-099, 150-199, 275-276
	Z	16	BJ	W0145	557B	24		34-61-26	050-099, 150-199, 275-276
	Z	165	BJ	W0135	177	22		31-31-22	ALL
	Z	165	BJ	W0135	771	22		31-31-22	ALL
	Z	165	BJ	W0135	772	22		31-31-22	ALL
	Z	165	BJ	W0135	773	22		31-31-22	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 188

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Z	165	BJ	W0135	774	22		31-31-22	ALL
	Z	166	BJ	W0135	179	22		31-31-22	ALL
	Z	166	BJ	W0135	180	22		31-31-22	ALL
	Z	166	BJ	W0135	181	22		31-31-22	ALL
	Z	166	BJ	W0135	188	22		31-31-22	ALL
	Z	166	BJ	W0155	018	22		31-31-22	ALL
	Z	181	BJ	W0135	525R	24		31-31-20	157, 167-199
	Z	181	BJ	W0145	264R	24		34-51-21	275-276
	Z	181	BJ	W0145	281R	24		34-55-21	157, 167-199
	Z	181	BJ	W0145	284R	24		34-22-29	157, 167-199
	Z	181	BJ	W0145	291R	24		34-55-21	275-276
	Z	181	BJ	W0145	296R	24		34-61-25	275-276
	Z	181	BJ	W0145	554R	24		31-35-12	157, 167-199
	Z	181	BJ	W0145	704R	24		34-45-14	275-276
	Z	181	BJ	W0145	715R	24		34-61-27	157, 167-199
	Z	181	BJ	W0145	716R	24		34-61-27	275-276
	Z	181	BJ	W0145	902R	24		23-22-11	275-276
	Z	181	BJ	W0145	903R	24		34-53-21	275-276
	Z	182	BJ	W0135	525B	24		31-31-20	157, 167-199
	Z	182	BJ	W0145	264B	24		34-51-21	275-276
	Z	182	BJ	W0145	281B	24		34-55-21	157, 167-199
	Z	182	BJ	W0145	284B	24		34-22-29	157, 167-199
	Z	182	BJ	W0145	291B	24		34-55-21	275-276
	Z	182	BJ	W0145	296B	24		34-61-25	275-276
	Z	182	BJ	W0145	554B	24		31-35-12	157, 167-199
	Z	182	BJ	W0145	704B	24		34-45-14	275-276
	Z	182	BJ	W0145	715B	24		34-61-27	157, 167-199
	Z	182	BJ	W0145	716B	24		34-61-27	275-276
	Z	182	BJ	W0145	902B	24		23-22-11	275-276
	Z	182	BJ	W0145	903B	24		34-53-21	275-276
	Z	183	BJ	W0135	525R	24		31-31-20	275-276

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 189

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Z	183	BJ	W0145	281R	24		34-55-21	275-276
	Z	183	BJ	W0145	284R	24		34-22-29	275-276
	Z	183	BJ	W0145	554R	24		31-35-12	275-276
	Z	183	BJ	W0145	715R	24		34-61-27	275-276
	Z	184	BJ	W0135	525B	24		31-31-20	275-276
	Z	184	BJ	W0145	281B	24		34-55-21	275-276
	Z	184	BJ	W0145	284B	24		34-22-29	275-276
	Z	184	BJ	W0145	554B	24		31-35-12	275-276
	Z	184	BJ	W0145	715B	24		34-61-27	275-276
	G	2	2	W0135	302R	24		31-31-19	277-299
	G	2	2	W0135	305R	24		31-31-19	277-299
	G	2	2	W0135	719	24		31-31-19	277-299
	G	2	2	W0135	720	24		31-31-19	277-299
	Z	21	BJ	W0135	296R	24		34-61-15	277-299
	Z	21	BJ	W0145	204R	24		27-32-21	277-299
	Z	21	BJ	W0145	234R	24		34-61-25	277-299
	Z	21	BJ	W0145	266R	24		31-35-13	277-299
	Z	21	BJ	W0145	526R	24		34-21-21	277-299
	Z	21	BJ	W0145	557R	24		34-61-26	277-299
	Z	22	BJ	W0135	296B	24		34-61-15	277-299
	Z	22	BJ	W0145	204B	24		27-32-21	277-299
	Z	22	BJ	W0145	234B	24		34-61-25	277-299
	Z	22	BJ	W0145	266B	24		31-35-13	277-299
	Z	22	BJ	W0145	526B	24		34-21-21	277-299
	Z	22	BJ	W0145	557B	24		34-61-26	277-299
	Z	23	BJ	W0145	264R	24		34-51-21	277-299
	Z	23	BJ	W0145	291R	24		34-55-21	277-299
	Z	23	BJ	W0145	296R	24		34-61-25	277-299
	Z	23	BJ	W0145	716R	24		34-61-27	277-299
	Z	23	BJ	W0145	902R	24		23-22-11	277-299
	Z	23	BJ	W0145	903R	24		34-53-21	277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 190

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Z	24	BJ	W0145	264B	24		34-51-21	277-299
	Z	24	BJ	W0145	291B	24		34-55-21	277-299
	Z	24	BJ	W0145	296B	24		34-61-25	277-299
	G	24	2	W0145	704R	24		34-45-14	150-152
	Z	24	BJ	W0145	716B	24		34-61-27	277-299
	Z	24	BJ	W0145	902B	24		23-22-11	277-299
	Z	24	BJ	W0145	903B	24		34-53-21	277-299
	G	25	2	W0145	704B	24		34-45-14	150-152
	Z	35	BJ	W0135	202R	22		34-12-21	ALL
	Z	35	BJ	W0145	504R	20		34-12-21	ALL
	Z	35	BJ	W0145	524R	22		34-12-21	ALL
	Z	35	BJ	W0145	831	22		34-12-21	ALL
	Z	36	BJ	W0145	509R	20		34-12-21	ALL
	Z	36	BJ	W0145	510R	20		34-12-21	ALL
	Z	36	BJ	W0145	522R	22		34-12-21	ALL
	Z	36	BJ	W0145	832	22		34-12-21	ALL
	Z	39	BJ	W0135	510R	24		31-51-33	ALL
	Z	39	BJ	W0145	220R	24		34-61-22	ALL
	Z	39	BJ	W0145	253R	24		34-61-13	ALL
	Z	39	BJ	W0145	514R	24		34-12-22	ALL
	Z	39	BJ	W0145	542R	24		22-32-11	ALL
	Z	39	BJ	W0145	544R	24		31-41-33	ALL
	Z	39	BJ	W0145	573R	24		34-21-31	ALL
	Z	40	BJ	W0135	510B	24		31-51-33	ALL
	Z	40	BJ	W0145	220B	24		34-61-22	ALL
	Z	40	BJ	W0145	253B	24		34-61-13	ALL
	Z	40	BJ	W0145	514B	24		34-12-22	ALL
	Z	40	BJ	W0145	542B	24		22-32-11	ALL
	Z	40	BJ	W0145	544B	24		31-41-33	ALL
	Z	40	BJ	W0145	573B	24		34-21-31	ALL
	G	41	2	W0145	048	20		34-53-21	150-154

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 191

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	G	41	2	W0145	059	22		34-53-21	150-154
	G	41	2	W0145	076	22		34-53-21	150-154
	Z	45	BJ	W0145	203R	24		34-61-11	ALL
	Z	45	BJ	W0145	207R	24		34-61-21	ALL
	Z	45	BJ	W0145	222R	24		34-61-21	ALL
	Z	45	BJ	W0145	250R	24		31-35-11	ALL
	Z	45	BJ	W0145	286R	24		23-22-11	ALL
	Z	45	BJ	W0145	598R	22		23-25-13	150, 153-155, 162-165
	Z	45	BJ	W0145	598R	24		23-25-13	156-157, 166-199, 277-299
	Z	46	BJ	W0145	203B	24		34-61-11	ALL
	Z	46	BJ	W0145	207B	24		34-61-21	ALL
	Z	46	BJ	W0145	222B	24		34-61-21	ALL
	Z	46	BJ	W0145	250B	24		31-35-11	ALL
	Z	46	BJ	W0145	286B	24		23-22-11	ALL
	Z	46	BJ	W0145	598B	22		23-25-13	150, 153-155, 162-165
	Z	46	BJ	W0145	598B	24		23-25-13	156-157, 166-199, 277-299
	Z	51	BJ	W0135	211R	24		34-53-11	ALL
	Z	51	BJ	W0145	278R	24		34-53-21	ALL
	Z	51	BJ	W0145	511R	24		34-12-22	ALL
	Z	51	BJ	W0145	514R	24		34-12-22	ALL
	Z	51	BJ	W0145	530R	24		34-13-11	ALL
	Z	51	BJ	W0145	535R	24		21-31-21	ALL
	Z	51	BJ	W0145	536R	24		21-31-11	ALL
	Z	51	BJ	W0145	586R	24		34-12-22	ALL
	Z	52	BJ	W0135	211B	24		34-53-11	ALL
	Z	52	BJ	W0145	278B	24		34-53-21	ALL
	Z	52	BJ	W0145	511B	24		34-12-22	ALL
	Z	52	BJ	W0145	514B	24		34-12-22	ALL
	Z	52	BJ	W0145	530B	24		34-13-11	ALL
	Z	52	BJ	W0145	535B	24		21-31-21	ALL
	Z	52	BJ	W0145	536B	24		21-31-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 192

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Z	52	BJ	W0145	586B	24		34-12-22	ALL
	Z	55	BJ	W0145	221R	24		34-61-22	050-099, 150-199, 275-276
	Z	55	BJ	W0145	254R	24		34-61-13	050-099, 150-199, 275-276
	Z	55	BJ	W0145	259R	24		34-61-22	050-099, 150-199, 275-276
	Z	55	BJ	W0145	545R	24		31-35-13	050-099, 150-199, 275-276
	Z	55	BJ	W0145	559R	24		34-61-26	050-099, 150-199, 275-276
	Z	56	BJ	W0145	221B	24		34-61-22	050-099, 150-199, 275-276
	Z	56	BJ	W0145	254B	24		34-61-13	050-099, 150-199, 275-276
	Z	56	BJ	W0145	259B	24		34-61-22	050-099, 150-199, 275-276
	Z	56	BJ	W0145	545B	24		31-35-13	050-099, 150-199, 275-276
	Z	56	BJ	W0145	559B	24		34-61-26	050-099, 150-199, 275-276
	Z	57	BJ	W0135	597R	24		34-61-16	050-099, 150-199, 275-276
	Z	57	BJ	W0145	233R	24		34-61-25	050-099, 150-199, 275-276
	Z	57	BJ	W0145	242R	24		22-41-11	050-099, 150-199, 275-276
	Z	57	BJ	W0145	247R	24		34-61-25	050-099, 150-199, 275-276
	Z	57	BJ	W0145	295R	24		34-61-25	050-099, 150-199, 275-276
	Z	57	BJ	W0145	540R	24		34-61-25	050-099, 150-199, 275-276
	Z	58	BJ	W0135	597B	24		34-61-16	050-099, 150-199, 275-276
	Z	58	BJ	W0145	233B	24		34-61-25	050-099, 150-199, 275-276
	Z	58	BJ	W0145	242B	24		22-41-11	050-099, 150-199, 275-276
	Z	58	BJ	W0145	247B	24		34-61-25	050-099, 150-199, 275-276
	Z	58	BJ	W0145	295B	24		34-61-25	050-099, 150-199, 275-276
	Z	58	BJ	W0145	540B	24		34-61-25	050-099, 150-199, 275-276
	Z	59	BJ	W0145	823	22		34-12-22	ALL
	Z	59	BJ	W0145	825	22		34-12-22	ALL
	Z	59	BJ	W0145	850	22		34-12-22	ALL
	Z	59	BJ	W0145	855	22		34-12-22	ALL
	Z	59	BJ	W0145	856	22		34-12-22	ALL
	Z	59	BJ	W0145	865	22		34-12-22	050-099
	Z	61	BJ	W0135	01GR	24		34-12-61	ALL
	Z	61	BJ	W0145	513R	24		34-12-22	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 193

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Z	61	BJ	W0145	525R	24		34-21-21	ALL
	Z	61	BJ	W0145	571R	24		27-11-12	ALL
	Z	61	BJ	W0145	572R	24		34-13-21	ALL
	Z	62	BJ	W0135	01GB	24		34-12-61	ALL
	Z	62	BJ	W0145	513B	24		34-12-22	ALL
	Z	62	BJ	W0145	525B	24		34-21-21	ALL
	Z	62	BJ	W0145	571B	24		27-11-12	ALL
	Z	62	BJ	W0145	572B	24		34-13-21	ALL
	Z	65	BJ	W0145	146	24		34-61-26	ALL
	Z	65	BJ	W0145	662	24		34-61-26	150-154
	Z	65	BJ	W0145	663	24		34-61-26	150-154
	Z	65	BJ	W0145	664	24		34-61-26	150-154
	Z	65	BJ	W0145	691	24		34-61-26	050-099, 155-199, 275-299
	Z	65	BJ	W0145	692	24		34-61-26	050-099, 155-199, 275-299
	Z	65	BJ	W0145	693	24		34-61-26	050-099, 155-199, 275-299
	Z	65	BJ	W0145	866	24		34-61-25	ALL
	G	69	2	W0135	593B	22		31-31-25	ALL
	G	69	2	W0135	593R	22		31-31-25	ALL
	G	69	2	W0155	301B	18		31-31-25	ALL
	Z	77	BJ	W0145	221R	24		34-61-22	277-299
	Z	77	BJ	W0145	254R	24		34-61-13	277-299
	Z	77	BJ	W0145	259R	24		34-61-22	277-299
	Z	77	BJ	W0145	545R	24		31-35-13	277-299
	Z	77	BJ	W0145	559R	24		34-61-26	277-299
	Z	78	BJ	W0145	221B	24		34-61-22	277-299
	Z	78	BJ	W0145	254B	24		34-61-13	277-299
	Z	78	BJ	W0145	259B	24		34-61-22	277-299
	Z	78	BJ	W0145	545B	24		31-35-13	277-299
	Z	78	BJ	W0145	559B	24		34-61-26	277-299
	Z	79	BJ	W0135	597R	24		34-61-16	277-299
	Z	79	BJ	W0145	233R	24		34-61-25	277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 194

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Z	79	BJ	W0145	242R	24		22-41-11	277-299
	Z	79	BJ	W0145	247R	24		34-61-25	277-299
	Z	79	BJ	W0145	295R	24		34-61-25	277-299
	Z	79	BJ	W0145	540R	24		34-61-25	277-299
	Z	80	BJ	W0135	597B	24		34-61-16	277-299
	Z	80	BJ	W0145	233B	24		34-61-25	277-299
	Z	80	BJ	W0145	242B	24		22-41-11	277-299
	Z	80	BJ	W0145	247B	24		34-61-25	277-299
	Z	80	BJ	W0145	295B	24		34-61-25	277-299
	Z	80	BJ	W0145	540B	24		34-61-25	277-299
	R	A001	2	W0135	305Y	24		31-31-19	277-299
	X	A001	BJ	W0145	301R	24		23-51-12	050-099, 150-199, 275-276
	X	A001	BJ	W0145	302R	24		23-51-12	050-099, 150-199, 275-276
	Y	A003	BJ	W0135	293R	24		31-31-14	050-099, 150-199, 275-276
	R	A003	2	W0135	305B	24		31-31-19	277-299
	Y	A003	BJ	W0135	581R	24		31-35-12	050-099, 150-199, 275-276
	Y	A003	BJ	W0135	794R	24		31-31-14	050-099, 150-199, 275-276
	Y	A004	BJ	W0135	514R	24		31-31-14	050-099, 150-199, 275-276
	Y	A004	BJ	W0135	537R	24		31-31-14	050-099, 150-199, 275-276
	Y	A004	BJ	W0135	582R	24		31-35-12	050-099, 150-199, 275-276
	R	A004	2	W0135	721	24		31-31-19	277-299
	R	A005	2	W0135	739	24		31-31-21	277-299
	Y	A005	BJ	W0145	219R	24		34-61-22	050-099, 150-199, 275-276
	Y	A005	BJ	W0145	252R	24		34-61-13	050-099, 150-199, 275-276
	Y	A005	BJ	W0145	292R	24		34-61-22	050-099, 150-199, 275-276
	R	A006	2	W0135	718	24		31-31-19	277-299
	Y	A006	BJ	W0145	010	24		34-61-23	050-099, 150-199, 275-276
	Y	A006	BJ	W0145	022	24		34-61-13	050-099, 150-199, 275-276
	Y	A006	BJ	W0145	088	24		34-55-21	050-099, 150-199, 275-276
	Y	A006	BJ	W0145	091	24		34-55-21	050-099, 150-199, 275-276
	Y	A007	BJ	W0145	264R	24		34-51-21	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 195

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	A007	BJ	W0145	291R	24		34-55-21	050-099, 150-199
	Y	A007	BJ	W0145	296R	24		34-61-25	050-099, 150-199
	X	A007	BJ	W0145	301R	24		23-51-12	277-299
	X	A007	BJ	W0145	302R	24		23-51-12	277-299
	Y	A007	BJ	W0145	704R	24		34-45-14	050-099, 153-156, 162-166
	Y	A007	BJ	W0145	716R	24		34-61-27	157, 167-199
	X	A008	BJ	W0135	05A	24		34-61-27	275-299
	Y	A008	BJ	W0145	150	24		31-51-33	050-099, 150-199, 275-276
	X	A008	BJ	W0145	717	24		34-61-27	275-299
	Y	A008	BJ	W0145	861	24		31-41-16	050-099, 150-199, 275-276
	Y	A008	BJ	W0145	862	24		31-51-33	050-099, 150-199, 275-276
	Y	A009	BJ	W0135	293R	24		31-31-14	277-299
	Y	A009	BJ	W0135	581R	24		31-35-12	277-299
	Y	A009	BJ	W0135	794R	24		31-31-14	277-299
	Y	A009	BJ	W0145	055	24		34-51-21	050-099, 150-199, 275-276
	Y	A009	BJ	W0145	089	24		34-55-21	050-099, 150-199, 275-276
	Y	A009	BJ	W0145	090	24		34-55-21	050-099, 150-199, 275-276
	Y	A009	BJ	W0145	097	24		34-31-21	050-099, 150-199, 275-276
	Y	A010	BJ	W0135	514R	24		31-31-14	277-299
	Y	A010	BJ	W0135	537R	24		31-31-14	277-299
	Y	A010	BJ	W0135	582R	24		31-35-12	277-299
	Y	A011	BJ	W0135	573R	24		31-31-20	050-099, 150-199, 275-276
	Y	A011	BJ	W0145	219R	24		34-61-22	277-299
	Y	A011	BJ	W0145	252R	24		34-61-13	277-299
	Y	A011	BJ	W0145	292R	24		34-61-22	277-299
	Y	A011	BJ	W0145	553R	24		31-35-12	050-099, 150-199, 275-276
	Y	A011	BJ	W0155	207R	24		31-31-20	050-099, 150-199, 275-276
	Y	A012	BJ	W0135	574R	24		31-31-20	050-099, 150-199, 275-276
	Y	A012	BJ	W0145	010	24		34-61-23	277-299
	Y	A012	BJ	W0145	022	24		34-61-13	277-299
	Y	A012	BJ	W0145	088	24		34-55-21	277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 196

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	A012	BJ	W0145	091	24		34-55-21	277-299
	Y	A012	BJ	W0145	506R	24		31-35-12	050-099, 150-199, 275-276
	Y	A012	BJ	W0155	208R	24		31-31-20	050-099, 150-199, 275-276
	Y	A013	BJ	W0145	218R	24		34-61-22	050-099, 150-199, 275-276
	Y	A013	BJ	W0145	251R	24		34-61-13	050-099, 150-199, 275-276
	Y	A013	BJ	W0145	261R	24		34-51-21	050-099, 150-199, 275-276
	Y	A013	BJ	W0145	269R	24		34-51-21	050-099, 150-199, 275-276
	Y	A014	BJ	W0145	150	24		31-51-33	277-299
	Y	A014	BJ	W0145	861	24		31-41-16	277-299
	Y	A014	BJ	W0145	862	24		31-51-33	277-299
	Y	A015	BJ	W0145	055	24		34-51-21	277-299
	Y	A015	BJ	W0145	089	24		34-55-21	277-299
	Y	A015	BJ	W0145	090	24		34-55-21	277-299
	Y	A015	BJ	W0145	097	24		34-31-21	277-299
	Y	A017	BJ	W0135	573R	24		31-31-20	277-299
	R	A017	2	W0135	721	24		31-31-19	050-099, 150-199, 275-276
	Y	A017	BJ	W0145	553R	24		31-35-12	277-299
	Y	A017	BJ	W0155	207R	24		31-31-20	277-299
	Y	A018	BJ	W0135	574R	24		31-31-20	277-299
	R	A018	2	W0135	718	24		31-31-19	050-099, 150-199, 275-276
	Y	A018	BJ	W0145	506R	24		31-35-12	277-299
	Y	A018	BJ	W0155	208R	24		31-31-20	277-299
	Y	A019	BJ	W0135	276R	24		34-61-14	277-299
	Y	A019	BJ	W0135	302R	24		31-31-19	050-099, 150-199, 275-276
	Y	A019	BJ	W0135	305R	24		31-31-19	050-099, 150-199, 275-276
	Y	A019	BJ	W0135	681R	24		34-61-14	277-299
	Y	A019	BJ	W0135	719	24		31-31-19	050-099, 150-199, 275-276
	Y	A019	BJ	W0135	720	24		31-31-19	050-099, 150-199, 275-276
	Y	A019	BJ	W0145	641R	24		34-61-24	277-299
	Y	A020	BJ	W0135	598R	24		34-61-16	275-299
	Y	A020	BJ	W0145	709R	24		34-61-25	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 197

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	A020	BJ	W0145	726R	24		34-61-25	157
	R	A021	2	W0135	305B	24		31-31-19	050-099, 150-199, 275-276
	R	A022	2	W0135	305Y	24		31-31-19	050-099, 150-199, 275-276
	R	A023	2	W0135	739	24		31-31-21	050-099, 150-199, 275-276
	R	A024	2	W0135	741	24		31-31-21	050-099, 150-199, 275-276
	Y	A025	BJ	W0145	218R	24		34-61-22	277-299
	Y	A025	BJ	W0145	251R	24		34-61-13	277-299
	Y	A025	BJ	W0145	261R	24		34-51-21	277-299
	Y	A025	BJ	W0145	269R	24		34-51-21	277-299
	R	A025	2	W0145	631	24		31-31-21	050-099, 150-199, 275-276
	R	A026	2	W0135	745	24		31-31-21	050-099, 150-199, 275-276
	R	A027	2	W0135	724	24		31-31-21	050-099, 150-199, 275-276
	R	A027	2	W0135	783	24		31-31-21	050-099, 150-199, 275-276
	R	A028	2	W0135	723	24		31-31-21	050-099, 150-199, 275-276
	R	A028	2	W0135	724	24		31-31-21	050-099, 150-199, 275-276
	Y	A029	BJ	W0135	804R	24		31-35-12	ALL
	Y	A029	BJ	W0145	537R	24		31-31-12	ALL
	Y	A029	BJ	W0145	586R	24		34-12-22	ALL
	Y	A031	BJ	W0145	803	24		34-12-22	ALL
	Y	A031	BJ	W0145	858	24		34-12-22	ALL
	Y	A031	BJ	W0145	859	24		31-51-21	ALL
	Y	A031	BJ	W0145	882	24		34-12-62	ALL
	Y	A032	BJ	W0135	850	24		34-61-15	ALL
	Y	A032	BJ	W0145	687	24		34-61-15	ALL
	Y	A032	BJ	W0145	688	24		34-61-15	ALL
	Y	A033	BJ	W0135	525R	24		31-31-20	050-099, 150-156, 162-166
	Y	A033	BJ	W0145	281R	24		34-55-21	050-099, 150-156, 162-166
	Y	A033	BJ	W0145	284R	24		34-22-29	050-099, 150-156, 162-166
	Y	A033	BJ	W0145	554R	24		31-35-12	050-099, 150-156, 162-166
	Y	A034	BJ	W0135	576R	24		31-31-20	ALL
	Y	A034	BJ	W0145	243R	24		31-31-20	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 198

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	A034	BJ	W0145	551R	24		31-35-12	ALL
	X	A037	BJ	W0135	657	22		31-31-18	ALL
	X	A037	BJ	W0145	123	22		31-31-18	ALL
	X	A038	BJ	W0135	184	24		31-31-22	ALL
	X	A038	BJ	W0145	567	24		31-51-21	ALL
	X	A042	BJ	W0135	652	24		31-31-19	ALL
	X	A042	BJ	W0145	849	24		31-31-19	ALL
	Y	A043	BJ	W0135	599R	24		34-61-16	ALL
	Y	A043	BJ	W0135	792R	24		34-61-24	ALL
	Y	A043	BJ	W0145	288R	24		34-61-24	ALL
	Y	A044	BJ	W0135	195	22		34-22-38	ALL
	Y	A044	BJ	W0135	685	22		34-22-38	ALL
	Y	A044	BJ	W0145	654	24		34-61-26	ALL
	X	A047	BJ	W0135	797	24		31-31-19	050-099, 150-199, 275-276
	X	A047	BJ	W0145	195	24		31-31-19	050-099, 150-199, 275-276
	X	A048	BJ	W0135	588R	24		31-31-22	050-099, 150-199, 275-276
	X	A048	BJ	W0155	213R	24		31-31-22	050-099, 150-199, 275-276
	Y	A049	BJ	W0135	588B	24		31-31-22	050-099, 150-199, 275-276
	Y	A049	BJ	W0135	824	20		31-31-22	050-099, 150-199, 275-276
	Y	A049	BJ	W0155	213B	24		31-31-22	050-099, 150-199, 275-276
	Y	A050	BJ	W0135	538B	24		31-31-22	050-099, 150-199, 275-276
	Y	A050	BJ	W0135	778B	24		31-31-22	050-099, 150-199, 275-276
	Y	A050	BJ	W0135	827	20		31-31-22	050-099, 150-199, 275-276
	Y	A053	BJ	W0145	375R	24		34-12-21	ALL
	Y	A053	BJ	W0145	377R	24		34-12-21	ALL
	Y	A053	BJ	W0145	378R	24		34-12-21	ALL
	Y	A054	BJ	W0145	375Y	24		34-12-21	ALL
	Y	A054	BJ	W0145	377Y	24		34-12-21	ALL
	Y	A054	BJ	W0145	378Y	24		34-12-21	ALL
	Y	A063	BJ	W0145	204R	24		27-32-21	050, 150, 152-199
	Y	A063	BJ	W0145	241R	24		22-32-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 199

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	A063	BJ	W0145	587R	24		34-61-26	ALL
	Y	A063	BJ	W0145	588R	24		34-61-26	ALL
	X	A068	BJ	W0145	570R	24		28-41-11	ALL
	X	A068	BJ	W0155	212R	24		28-41-11	ALL
	F	A070	2	W0135	592R	22		31-31-25	ALL
	F	A070	2	W0155	301R	18		31-31-25	ALL
	R	A071	2	W0135	812	24		31-31-26	050-099, 150-199, 275-276
	R	A071	2	W0135	841	24		31-31-26	050-099, 150-199, 275-276
	Y	A073	BJ	W0135	600R	24		34-61-14	277-299
	R	A073	2	W0135	813	24		31-31-26	050-099, 150-199, 275-276
	Y	A073	BJ	W0145	223R	24		34-61-24	277-299
	Y	A073	BJ	W0145	271R	24		34-61-24	277-299
	R	A073	2	W0145	800	24		31-31-26	050-099, 150-199, 275-276
	Y	A074	BJ	W0145	651	24		34-53-22	050-099, 155-164, 166-199, 275-299
	Y	A074	2	W0145	651	24		34-53-22	165
	Y	A074	BJ	W0145	667	24		34-53-22	050-099, 155-164, 166-199, 275-299
	Y	A074	2	W0145	667	24		34-53-22	165
	Y	A074	BJ	W0145	668	24		34-53-22	050-099, 155-164, 166-199, 275-299
	Y	A074	2	W0145	668	24		34-53-22	165
	Y	A075	BJ	W0135	600R	24		34-61-14	157, 167-199, 275-276
	Y	A075	BJ	W0145	223R	24		34-61-24	157, 167-199, 275-276
	Y	A075	BJ	W0145	224R	24		34-61-24	275-276
	Y	A075	BJ	W0145	271R	24		34-61-24	157, 167-199
	D	A076	2	W0145	866	24		34-61-25	050-099, 150-199, 275-276
	Y	A077	BJ	W0135	276R	24		34-61-14	157, 167-199, 275-276
	Y	A077	BJ	W0135	681R	24		34-61-14	157, 167-199, 275-276
	Y	A077	BJ	W0145	641R	24		34-61-24	157, 167-199, 275-276
	Y	A078	BJ	W0135	060	24		34-61-17	157, 167-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 200

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	A078	BJ	W0145	119	24		34-61-17	157, 167-199
	Y	A078	BJ	W0145	720	24		34-61-27	157, 167-199
	X	A083	BJ	W0135	797	24		31-31-19	277-299
	X	A083	BJ	W0145	195	24		31-31-19	277-299
	X	A084	BJ	W0135	588R	24		31-31-22	277-299
	X	A084	BJ	W0155	213R	24		31-31-22	277-299
	Y	A085	BJ	W0135	588B	24		31-31-22	277-299
	Y	A085	BJ	W0135	824	20		31-31-22	277-299
	Y	A085	BJ	W0155	213B	24		31-31-22	277-299
	Y	A086	BJ	W0135	538B	24		31-31-22	277-299
	Y	A086	BJ	W0135	778B	24		31-31-22	277-299
	Y	A086	BJ	W0135	827	20		31-31-22	277-299
	R	A087	2	W0135	035	22		31-31-18	278
	R	A087	2	W0135	051	22		31-31-18	278
	D	A088	2	W0135	682	24		34-61-17	157, 167-199
	D	A088	2	W0145	692	24		34-61-26	278
	D	A088	2	W0145	718	24		34-61-27	157, 167-199
	X	A089	BJ	W0135	253R	24		31-35-15	050-099, 150-199, 275-276
	D	A089	2	W0135	682	24		34-61-17	275-299
	X	A089	BJ	W0145	696R	24		31-35-15	050-099, 150-199, 275-276
	D	A089	2	W0145	718	24		34-61-27	275-299
	R	A090	2	W0135	812	24		31-31-26	277-299
	R	A090	2	W0135	841	24		31-31-26	277-299
	D	A090	2	W0145	896	22		34-12-62	050-099, 162-166
	D	A090	2	W0145	898	20		34-12-62	050-099, 162-166
	R	A091	2	W0135	813	24		31-31-26	277-299
	R	A091	2	W0145	800	24		31-31-26	277-299
	D	A091	2	W0145	896	22		34-12-62	157, 167-199
	D	A091	2	W0145	898	20		34-12-62	157, 167-199
	D	A092	2	W0145	692	24		34-61-26	050-099, 155-199, 275-277, 280-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 201

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	D	A092	2	W0145	896	22		34-12-62	152
	D	A092	2	W0145	898	20		34-12-62	152
	D	A093	2	W0145	691	24		34-61-26	050-099, 155-199, 275-299
	D	A094	2	W0145	693	24		34-61-26	050-099, 155-199, 275-299
	R	A095	2	W0135	051	22		31-31-18	277-299
	R	A095	2	W0135	052	22		31-31-18	277-299
	D	A096	2	W0145	638	24		31-51-41	277-299
	D	A096	2	W0145	639	24		31-51-41	277-299
	D	A097	2	W0145	639	24		31-51-41	277-299
	Y	A101	BJ	W0135	577R	24		31-31-20	050-099, 150-199, 275-276
	R	A101	2	W0135	741	24		31-31-21	277-299
	Y	A101	BJ	W0145	249R	24		31-31-20	050-099, 150-199, 275-276
	Y	A101	BJ	W0145	552R	24		31-35-12	050-099, 150-199, 275-276
	R	A102	2	W0145	631	24		31-31-21	277-299
	Y	A103	BJ	W0135	575R	24		31-31-20	050-099, 150-199, 275-276
	R	A103	2	W0135	745	24		31-31-21	277-299
	Y	A103	BJ	W0145	502R	24		31-35-12	050-099, 150-199, 275-276
	Y	A103	BJ	W0155	209R	24		31-31-20	050-099, 150-199, 275-276
	R	A104	2	W0135	724	24		31-31-21	277-299
	R	A104	2	W0135	783	24		31-31-21	277-299
	R	A105	2	W0135	723	24		31-31-21	277-299
	R	A105	2	W0135	724	24		31-31-21	277-299
	X	A105	BJ	W0135	817	24		31-31-26	050-099, 150-199, 275-276
	X	A105	BJ	W0145	658	24		31-31-26	050-099, 150-199, 275-276
	X	A107	BJ	W0135	192	22		31-31-14	050-099, 150-199, 275-276
	Y	A107	BJ	W0135	577R	24		31-31-20	277-299
	X	A107	BJ	W0145	075	22		31-31-14	050-099, 150-199, 275-276
	Y	A107	BJ	W0145	249R	24		31-31-20	277-299
	Y	A107	BJ	W0145	552R	24		31-35-12	277-299
	X	A108	BJ	W0135	080	24		31-31-17	050-099, 150-199, 275-276
	X	A108	BJ	W0145	111	24		31-31-17	050-099, 150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 202

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	A109	BJ	W0135	562R	24		31-31-20	050-099, 150-199, 275-276
	Y	A109	BJ	W0135	563R	24		31-31-20	050-099, 150-199, 275-276
	Y	A109	BJ	W0135	575R	24		31-31-20	277-299
	Y	A109	BJ	W0145	502R	24		31-35-12	277-299
	Y	A109	BJ	W0145	555R	24		31-35-12	050-099, 150-199, 275-276
	Y	A109	BJ	W0155	209R	24		31-31-20	277-299
	Y	A111	BJ	W0135	566R	24		31-31-20	050-099, 150-199, 275-276
	Y	A111	BJ	W0135	567R	24		31-31-20	050-099, 150-199, 275-276
	X	A111	BJ	W0135	817	24		31-31-26	277-299
	Y	A111	BJ	W0145	503R	24		31-35-12	050-099, 150-199, 275-276
	X	A111	BJ	W0145	658	24		31-31-26	277-299
	Y	A112	BJ	W0135	852	24		34-61-14	050-099, 150-199, 276
	Y	A112	BJ	W0135	854	24		34-61-14	050-099, 150-199, 276
	Y	A112	BJ	W0135	855	24		34-61-24	050-099, 155-199, 276
	Y	A112	BJ	W0145	695	24		34-61-24	050-099, 155-199, 276
	X	A113	BJ	W0135	192	22		31-31-14	277-299
	Y	A113	BJ	W0135	568R	24		31-31-20	050-099, 150-199, 275-276
	Y	A113	BJ	W0135	570R	24		31-31-20	050-099, 150-199, 275-276
	X	A113	BJ	W0145	075	22		31-31-14	277-299
	Y	A113	BJ	W0145	507R	24		31-35-12	050-099, 150-199, 275-276
	X	A114	BJ	W0135	080	24		31-31-17	277-299
	Y	A114	BJ	W0135	571R	24		31-31-20	050-099, 150-199, 275-276
	Y	A114	BJ	W0135	572R	24		31-31-20	050-099, 150-199, 275-276
	X	A114	BJ	W0145	111	24		31-31-17	277-299
	Y	A114	BJ	W0145	501R	24		31-35-12	050-099, 150-199, 275-276
	Y	A115	BJ	W0135	562R	24		31-31-20	277-299
	Y	A115	BJ	W0135	563R	24		31-31-20	277-299
	Y	A115	BJ	W0145	555R	24		31-35-12	277-299
	R	A116	2	W0135	051	22		31-31-18	050-099, 150-199, 275-276
	R	A116	2	W0135	052	22		31-31-18	050-099, 150-199, 275-276
	R	A117	2	W0135	035	22		31-31-18	050-099, 150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 203

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	R	A117	2	W0135	051	22		31-31-18	050-099, 150-199, 275-276
	Y	A117	BJ	W0135	566R	24		31-31-20	277-299
	Y	A117	BJ	W0135	567R	24		31-31-20	277-299
	Y	A117	BJ	W0145	503R	24		31-35-12	277-299
	X	A118	BJ	W0135	299R	24		34-45-12	153-154
	Y	A118	BJ	W0135	852	24		34-61-14	277-299
	Y	A118	BJ	W0135	854	24		34-61-14	277-299
	Y	A118	BJ	W0135	855	24		34-61-24	277-299
	X	A118	BJ	W0135	857R	24		34-45-12	050-099, 150-152, 155-199
	X	A118	BJ	W0145	675R	24		34-45-12	050-099, 150-199, 275-276
	Y	A118	BJ	W0145	695	24		34-61-24	277-299
	X	A119	BJ	W0135	299B	24		34-45-12	153-154
	Y	A119	BJ	W0135	568R	24		31-31-20	277-299
	Y	A119	BJ	W0135	570R	24		31-31-20	277-299
	X	A119	BJ	W0135	857B	24		34-45-12	050-099, 150-152, 155-199
	Y	A119	BJ	W0145	507R	24		31-35-12	277-299
	X	A119	BJ	W0145	675B	24		34-45-12	050-099, 150-199, 275-276
	R	A120	2	W0135	035	22		31-31-18	050-099, 150-199, 275-276
	R	A120	2	W0135	036	22		31-31-18	050-099, 150-199, 275-276
	Y	A120	BJ	W0135	571R	24		31-31-20	277-299
	Y	A120	BJ	W0135	572R	24		31-31-20	277-299
	Y	A120	BJ	W0145	501R	24		31-35-12	277-299
	R	A121	2	W0135	036	22		31-31-18	050-099, 150-199, 275-276
	R	A121	2	W0135	037	22		31-31-18	050-099, 150-199, 275-276
	R	A122	2	W0135	037	22		31-31-18	050-099, 150-199, 275-276
	R	A122	2	W0135	038	22		31-31-18	050-099, 150-199, 275-276
	R	A123	2	W0135	038	22		31-31-18	050-099, 150-199, 275-276
	X	A123	BJ	W0135	857R	24		34-45-12	277-299
	X	A123	BJ	W0145	675R	24		34-45-12	277-299
	X	A124	BJ	W0135	857B	24		34-45-12	277-299
	X	A124	BJ	W0145	675B	24		34-45-12	277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 204

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	D	A125	2	W0145	638	24		31-51-41	150-199, 275-276
	D	A125	2	W0145	639	24		31-51-41	150-199, 275-276
	D	A126	2	W0145	639	24		31-51-41	150-199, 275-276
	D	A127	2	W0135	064	24		31-31-11	050-099, 150-199, 275-276
	Y	A129	BJ	W0135	218R	24		31-31-11	ALL
	Y	A129	BJ	W0135	219R	24		31-31-11	ALL
	Y	A129	BJ	W0135	223R	24		31-31-11	ALL
	Y	A130	BJ	W0135	753	22		31-35-11	050-099, 150-154, 275-299
	Y	A130	BJ	W0135	762	22		31-35-11	050-099, 150-154, 275-299
	Y	A133	BJ	W0135	598R	24		34-61-16	050-099, 150-156, 162-166
	Y	A133	BJ	W0145	245R	24		34-22-28	ALL
	Y	A133	BJ	W0145	248R	24		34-61-25	ALL
	Y	A133	BJ	W0145	260R	24		31-35-13	ALL
	Y	A133	BJ	W0145	726R	24		34-61-25	157, 167-199
	Y	A134	BJ	W0135	076	22		31-31-11	ALL
	Y	A134	BJ	W0135	101	22		31-31-11	ALL
	Y	A134	BJ	W0135	102	22		31-31-11	ALL
	Y	A134	BJ	W0145	107	22		31-31-11	ALL
	Y	A135	BJ	W0145	267R	24		34-51-21	ALL
	Y	A135	BJ	W0145	285R	24		34-22-29	ALL
	Y	A135	BJ	W0155	210R	24		31-35-13	ALL
	Y	A139	BJ	W0135	002	22		34-22-17	ALL
	Y	A139	BJ	W0135	050	24		31-31-12	ALL
	Y	A139	BJ	W0145	104	24		31-31-12	ALL
	Y	A140	BJ	W0135	832	24		34-61-16	ALL
	Y	A140	BJ	W0145	677	24		34-61-16	ALL
	Y	A140	BJ	W0145	678	24		34-61-26	ALL
	X	A141	BJ	W0135	226R	24		31-31-14	ALL
	X	A141	BJ	W0145	529R	24		31-31-14	ALL
	X	A142	BJ	W0135	226B	24		31-31-14	ALL
	X	A142	BJ	W0145	529B	24		31-31-14	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 205

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	A143	BJ	W0135	230R	24		31-31-12	ALL
	Y	A143	BJ	W0135	579R	24		31-35-12	ALL
	Y	A143	BJ	W0145	516R	24		31-31-12	ALL
	Y	A144	BJ	W0135	275R	24		31-31-13	ALL
	Y	A144	BJ	W0135	580R	24		31-35-12	ALL
	Y	A144	BJ	W0135	793R	24		31-31-13	ALL
	Y	A144	BJ	W0145	574R	24		23-22-11	ALL
	X	A145	BJ	W0135	565R	24		31-31-20	ALL
	X	A145	BJ	W0145	289R	24		31-31-20	ALL
	X	A146	BJ	W0135	005	22		31-31-11	ALL
	X	A146	BJ	W0145	102	22		31-31-11	ALL
	Y	A147	BJ	W0145	013	24		34-61-24	ALL
	Y	A147	BJ	W0145	161	24		34-61-24	ALL
	Y	A147	BJ	W0145	162	24		34-61-24	ALL
	Y	A148	BJ	W0135	176	24		31-31-19	ALL
	Y	A148	BJ	W0145	653	24		34-61-26	ALL
	Y	A148	BJ	W0145	665	24		34-61-26	ALL
	X	A149	BJ	W0135	149	24		31-31-18	ALL
	X	A149	BJ	W0145	178	24		31-31-18	ALL
	X	A151	BJ	W0135	153	24		31-31-18	ALL
	X	A151	BJ	W0145	181	24		31-31-18	ALL
	X	A152	BJ	W0145	216R	24		34-61-22	ALL
	X	A152	BJ	W0155	201R	24		34-61-22	ALL
	Y	A155	BJ	W0145	173	24		34-61-25	ALL
	Y	A155	BJ	W0145	174	24		34-61-25	ALL
	Y	A155	BJ	W0145	847	24		34-61-25	ALL
	X	A157	BJ	W0135	203R	24		34-61-23	ALL
	X	A157	BJ	W0145	214R	24		34-61-23	ALL
	X	A158	BJ	W0135	007	24		34-61-23	ALL
	X	A158	BJ	W0145	011	22		34-61-23	ALL
	X	A159	BJ	W0135	205R	24		34-61-23	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 206

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	A159	BJ	W0145	213R	24		34-61-23	ALL
	X	A160	BJ	W0135	001	24		34-61-23	ALL
	X	A160	BJ	W0145	012	24		34-61-23	ALL
	X	A161	BJ	W0135	209R	24		34-61-11	ALL
	X	A161	BJ	W0145	201R	24		34-61-11	ALL
	X	A162	BJ	W0135	748	24		31-31-22	ALL
	X	A162	BJ	W0145	633	24		31-31-22	ALL
	Y	A167	BJ	W0145	01DR	24		34-12-62	ALL
	Y	A167	BJ	W0145	505R	24		34-12-22	ALL
	Y	A167	BJ	W0145	515R	24		34-12-22	ALL
	Y	A168	BJ	W0135	655	24		31-31-19	ALL
	Y	A168	BJ	W0145	101	22		34-12-62	ALL
	Y	A168	BJ	W0145	669	24		34-53-21	ALL
	Y	A168	BJ	W0145	848	24		34-21-21	ALL
	X	A169	BJ	W0135	301R	24		34-12-21	ALL
	X	A169	BJ	W0145	376R	24		34-12-21	ALL
	Y	A179	BJ	W0135	840R	24		34-61-11	ALL
	Y	A179	BJ	W0145	299R	24		34-61-21	ALL
	Y	A179	BJ	W0145	685R	24		34-61-21	ALL
	Y	A180	BJ	W0135	598R	24		34-61-16	157, 167-199
	Y	A180	BJ	W0145	709R	24		34-61-25	157, 167-199
	Y	A180	BJ	W0145	726R	24		34-61-25	167-199
	D	A184	2	W0145	896	22		34-12-62	150-151, 153-156, 277-299
	D	A184	2	W0145	898	20		34-12-62	150-151, 153-156, 277-299
	Y	A185	BJ	W0135	011	24		34-12-61	150-151, 153-199, 275-299
	Y	A185	BJ	W0145	749	24		34-12-62	150-151, 153-199, 275-299
	Y	A186	BJ	W0135	672	24		34-12-62	ALL
	Y	A186	BJ	W0145	751	24		34-12-62	ALL
	R	A187	2	W0135	891	24		31-31-17	ALL
	R	A188	2	W0135	891	24		31-31-17	ALL
	R	A188	2	W0135	892	24		31-31-17	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 207

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	D	A189	2	W0135	883	24		34-61-27	157, 167-199, 275-299
	D	A190	2	W0145	866	24		34-61-25	277-299
	D	A190	2	W0145	896	22		34-12-62	275-276
	D	A190	2	W0145	898	20		34-12-62	275-276
	D	A191	2	W0135	064	24		31-31-11	277-299
	R	A192	2	W0135	035	22		31-31-18	277, 280-299
	R	A192	2	W0135	051	22		31-31-18	277, 280-299
	R	A193	2	W0135	035	22		31-31-18	277-299
	R	A193	2	W0135	036	22		31-31-18	277-299
	Y	A194	BJ	W0135	011	24		34-12-61	050-099, 152
	R	A194	2	W0135	036	22		31-31-18	277-299
	R	A194	2	W0135	037	22		31-31-18	277-299
	Y	A194	BJ	W0145	749	24		34-12-62	050-099, 152
	R	A195	2	W0135	037	22		31-31-18	277-299
	R	A195	2	W0135	038	22		31-31-18	277-299
	R	A196	2	W0135	038	22		31-31-18	277-299
	D	A197	2	W0135	165	24		34-61-27	157, 167-199, 277-299
	X	B001	BJ	W0145	301B	24		23-51-12	050-099, 150-199, 275-276
	X	B001	BJ	W0145	302B	24		23-51-12	050-099, 150-199, 275-276
	X	B002	BJ	W0135	135	24		31-31-21	050-099, 150-199, 275-276
	X	B002	BJ	W0145	632	24		31-31-21	050-099, 150-199, 275-276
	X	B007	BJ	W0145	301B	24		23-51-12	277-299
	X	B007	BJ	W0145	302B	24		23-51-12	277-299
	X	B008	BJ	W0135	135	24		31-31-21	277-299
	X	B008	BJ	W0145	632	24		31-31-21	277-299
	X	B037	BJ	W0135	796	22		31-31-18	ALL
	X	B037	BJ	W0145	122	22		31-31-18	ALL
	X	B042	BJ	W0135	653	24		31-31-19	ALL
	X	B042	BJ	W0145	854	24		31-31-19	ALL
	X	B047	BJ	W0135	849	24		34-61-15	050-099, 150-199, 275-276
	X	B047	BJ	W0145	686	24		34-61-15	050-099, 150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 208

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	B048	BJ	W0135	589R	24		31-31-22	050-099, 150-199, 275-276
	X	B048	BJ	W0135	590R	24		31-31-22	050-099, 150-199, 275-276
	X	B068	BJ	W0145	570B	24		28-41-11	ALL
	X	B068	BJ	W0155	212B	24		28-41-11	ALL
	X	B083	BJ	W0135	849	24		34-61-15	277-299
	X	B083	BJ	W0145	686	24		34-61-15	277-299
	X	B084	BJ	W0135	589R	24		31-31-22	277-299
	X	B084	BJ	W0135	590R	24		31-31-22	277-299
	X	B089	BJ	W0135	253B	24		31-35-15	050-099, 150-199, 275-276
	X	B089	BJ	W0145	696B	24		31-35-15	050-099, 150-199, 275-276
	X	B105	BJ	W0135	818	24		31-31-26	050-099, 150-199, 275-276
	X	B105	BJ	W0155	016	24		31-31-26	050-099, 150-199, 275-276
	X	B107	BJ	W0135	822	24		31-31-26	050-099, 150-199, 275-276
	X	B107	BJ	W0155	017	24		31-31-26	050-099, 150-199, 275-276
	X	B111	BJ	W0135	818	24		31-31-26	277-299
	X	B111	BJ	W0155	016	24		31-31-26	277-299
	X	B113	BJ	W0135	822	24		31-31-26	277-299
	X	B113	BJ	W0155	017	24		31-31-26	277-299
	X	B118	BJ	W0135	833R	24		34-45-12	050-099, 150-199
	X	B118	BJ	W0145	676R	24		34-45-12	050-099, 150-199, 275-276
	X	B119	BJ	W0135	833B	24		34-45-12	050-099, 150-199
	X	B119	BJ	W0145	676B	24		34-45-12	050-099, 150-199, 275-276
	X	B123	BJ	W0135	833R	24		34-45-12	277-299
	X	B123	BJ	W0145	676R	24		34-45-12	277-299
	X	B124	BJ	W0135	833B	24		34-45-12	277-299
	X	B124	BJ	W0145	676B	24		34-45-12	277-299
	X	B141	BJ	W0145	116	24		31-31-17	050-099, 150-154, 162-163, 275-276
	X	B142	BJ	W0135	079	24		31-31-17	ALL
	X	B142	BJ	W0145	110	24		31-31-17	ALL
	X	B145	BJ	W0135	565B	24		31-31-20	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 209

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	B145	BJ	W0145	289B	24		31-31-20	ALL
	X	B149	BJ	W0135	150	24		31-31-18	ALL
	X	B149	BJ	W0145	177	24		31-31-18	ALL
	X	B151	BJ	W0135	154	24		31-31-18	ALL
	X	B151	BJ	W0145	182	24		31-31-18	ALL
	X	B152	BJ	W0145	216B	24		34-61-22	ALL
	X	B152	BJ	W0155	201B	24		34-61-22	ALL
	X	B157	BJ	W0135	203B	24		34-61-23	ALL
	X	B157	BJ	W0145	214B	24		34-61-23	ALL
	X	B158	BJ	W0135	018	24		34-12-12	ALL
	X	B158	BJ	W0145	827	24		34-12-12	ALL
	X	B159	BJ	W0135	205B	24		34-61-23	ALL
	X	B159	BJ	W0145	213B	24		34-61-23	ALL
	X	B161	BJ	W0135	209B	24		34-61-11	ALL
	X	B161	BJ	W0145	201B	24		34-61-11	ALL
	X	B169	BJ	W0135	301B	24		34-12-21	ALL
	X	B169	BJ	W0145	376B	24		34-12-21	ALL
	R	C001	2	W0135	302Y	24		31-31-19	277-299
	R	C001	2	W0135	718	24		31-31-19	277-299
	X	C001	BJ	W0145	293R	24		23-51-12	050-099, 150-199, 275-276
	X	C001	BJ	W0145	301Y	24		23-51-12	050-099, 150-199, 275-276
	Y	C003	BJ	W0135	293B	24		31-31-14	050-099, 150-199, 275-276
	R	C003	2	W0135	302B	24		31-31-19	277-299
	Y	C003	BJ	W0135	581B	24		31-35-12	050-099, 150-199, 275-276
	R	C003	2	W0135	721	24		31-31-19	277-299
	Y	C003	BJ	W0135	794B	24		31-31-14	050-099, 150-199, 275-276
	Y	C004	BJ	W0135	514B	24		31-31-14	050-099, 150-199, 275-276
	Y	C004	BJ	W0135	537B	24		31-31-14	050-099, 150-199, 275-276
	Y	C004	BJ	W0135	582B	24		31-35-12	050-099, 150-199, 275-276
	R	C004	2	W0135	720	24		31-31-19	277-299
	R	C005	2	W0135	740	24		31-31-21	277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 210

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	R	C005	2	W0135	741	24		31-31-21	277-299
	Y	C005	BJ	W0145	219B	24		34-61-22	050-099, 150-199, 275-276
	Y	C005	BJ	W0145	252B	24		34-61-13	050-099, 150-199, 275-276
	Y	C005	BJ	W0145	292B	24		34-61-22	050-099, 150-199, 275-276
	R	C006	2	W0135	719	24		31-31-19	277-299
	Y	C007	BJ	W0145	264B	24		34-51-21	050-099, 150-199
	Y	C007	BJ	W0145	291B	24		34-55-21	050-099, 150-199
	X	C007	BJ	W0145	293R	24		23-51-12	277-299
	Y	C007	BJ	W0145	296B	24		34-61-25	050-099, 150-199
	X	C007	BJ	W0145	301Y	24		23-51-12	277-299
	Y	C007	BJ	W0145	704B	24		34-45-14	050-099, 153-156, 162-166
	Y	C007	BJ	W0145	716B	24		34-61-27	157, 167-199
	Y	C009	BJ	W0135	293B	24		31-31-14	277-299
	Y	C009	BJ	W0135	581B	24		31-35-12	277-299
	Y	C009	BJ	W0135	794B	24		31-31-14	277-299
	Y	C009	BJ	W0145	023	22		34-61-13	050-099, 150-199, 275-276
	Y	C009	BJ	W0145	027	22		34-61-23	050-099, 150-199, 275-276
	Y	C009	BJ	W0145	054	22		34-51-21	050-099, 150-199, 275-276
	Y	C009	BJ	W0145	056	22		34-51-21	050-099, 150-199, 275-276
	Y	C010	BJ	W0135	514B	24		31-31-14	277-299
	Y	C010	BJ	W0135	537B	24		31-31-14	277-299
	Y	C010	BJ	W0135	582B	24		31-35-12	277-299
	Y	C011	BJ	W0135	573B	24		31-31-20	050-099, 150-199, 275-276
	Y	C011	BJ	W0145	219B	24		34-61-22	277-299
	Y	C011	BJ	W0145	252B	24		34-61-13	277-299
	Y	C011	BJ	W0145	292B	24		34-61-22	277-299
	Y	C011	BJ	W0145	553B	24		31-35-12	050-099, 150-199, 275-276
	Y	C011	BJ	W0155	207B	24		31-31-20	050-099, 150-199, 275-276
	Y	C012	BJ	W0135	060	24		34-61-17	277-299
	Y	C012	BJ	W0135	574B	24		31-31-20	050-099, 150-199, 275-276
	Y	C012	BJ	W0145	119	24		34-61-17	277-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 211

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	C012	BJ	W0145	506B	24		31-35-12	050-099, 150-199, 275-276
	Y	C012	BJ	W0145	720	24		34-61-27	277-299
	Y	C012	BJ	W0155	208B	24		31-31-20	050-099, 150-199, 275-276
	Y	C013	BJ	W0145	218B	24		34-61-22	050-099, 150-199, 275-276
	Y	C013	BJ	W0145	251B	24		34-61-13	050-099, 150-199, 275-276
	Y	C013	BJ	W0145	261B	24		34-51-21	050-099, 150-199, 275-276
	Y	C013	BJ	W0145	269B	24		34-51-21	050-099, 150-199, 275-276
	Y	C015	BJ	W0145	023	22		34-61-13	277-299
	Y	C015	BJ	W0145	027	22		34-61-23	277-299
	Y	C015	BJ	W0145	054	22		34-51-21	277-299
	Y	C015	BJ	W0145	056	22		34-51-21	277-299
	Y	C017	BJ	W0135	573B	24		31-31-20	277-299
	R	C017	2	W0135	720	24		31-31-19	050-099, 150-199, 275-276
	Y	C017	BJ	W0145	553B	24		31-35-12	277-299
	Y	C017	BJ	W0155	207B	24		31-31-20	277-299
	Y	C018	BJ	W0135	574B	24		31-31-20	277-299
	R	C018	2	W0135	719	24		31-31-19	050-099, 150-199, 275-276
	Y	C018	BJ	W0145	506B	24		31-35-12	277-299
	Y	C018	BJ	W0155	208B	24		31-31-20	277-299
	Y	C019	BJ	W0135	276B	24		34-61-14	277-299
	Y	C019	BJ	W0135	681B	24		34-61-14	277-299
	Y	C019	BJ	W0145	641B	24		34-61-24	277-299
	Y	C020	BJ	W0135	598B	24		34-61-16	275-299
	Y	C020	BJ	W0145	709B	24		34-61-25	275-299
	Y	C020	BJ	W0145	726B	24		34-61-25	157
	R	C021	2	W0135	302B	24		31-31-19	050-099, 150-199, 275-276
	R	C021	2	W0135	721	24		31-31-19	050-099, 150-199, 275-276
	R	C022	2	W0135	302Y	24		31-31-19	050-099, 150-199, 275-276
	R	C022	2	W0135	718	24		31-31-19	050-099, 150-199, 275-276
	R	C023	2	W0135	740	24		31-31-21	050-099, 150-199, 275-276
	R	C023	2	W0135	741	24		31-31-21	050-099, 150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 212

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		<b>284T0384 (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	D	<b>DIODEBLOCK (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	F	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	G	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	H	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	R	<b>RESISTORBLOCK (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	Z	<b>BACM15C3C (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
	R	C024	2	W0135	742	24		31-31-21	050-099, 150-199, 275-276
	R	C024	2	W0135	743	24		31-31-21	050-099, 150-199, 275-276
	R	C025	2	W0135	744	24		31-31-21	050-099, 150-199, 275-276
	R	C025	2	W0135	745	24		31-31-21	050-099, 150-199, 275-276
	Y	C025	BJ	W0145	218B	24		34-61-22	277-299
	Y	C025	BJ	W0145	251B	24		34-61-13	277-299
	Y	C025	BJ	W0145	261B	24		34-51-21	277-299
	Y	C025	BJ	W0145	269B	24		34-51-21	277-299
	R	C026	2	W0135	135	24		31-31-21	050-099, 150-199, 275-276
	R	C026	2	W0135	746	24		31-31-21	050-099, 150-199, 275-276
	R	C027	2	W0135	728	24		31-31-21	050-099, 150-199, 275-276
	R	C027	2	W0135	729	24		31-31-21	050-099, 150-199, 275-276
	R	C028	2	W0135	725	24		31-31-21	050-099, 150-199, 275-276
	R	C028	2	W0135	726	24		31-31-21	050-099, 150-199, 275-276
	Y	C029	BJ	W0135	804B	24		31-35-12	ALL
	Y	C029	BJ	W0145	537B	24		31-31-12	ALL
	Y	C029	BJ	W0145	586B	24		34-12-22	ALL
	Y	C030	BJ	W0135	01H	24		34-12-61	152
	Y	C030	BJ	W0145	857	24		34-12-22	152
	Y	C030	BJ	W0145	884	24		34-12-62	152
	Y	C031	BJ	W0145	801	20		34-12-21	ALL
	Y	C031	BJ	W0145	830	22		34-12-21	ALL
	Y	C031	BJ	W0145	834	22		34-12-21	ALL
	Y	C032	BJ	W0135	01H	24		34-12-61	150-151, 153-199, 275-299
	Y	C032	BJ	W0145	857	24		34-12-22	150-151, 153-199, 275-299
	Y	C032	BJ	W0145	884	24		34-12-62	150-151, 153-199, 275-299
	Y	C033	BJ	W0135	525B	24		31-31-20	050-099, 150-156, 162-166
	Y	C033	BJ	W0145	281B	24		34-55-21	050-099, 150-156, 162-166
	Y	C033	BJ	W0145	284B	24		34-22-29	050-099, 150-156, 162-166
	Y	C033	BJ	W0145	554B	24		31-35-12	050-099, 150-156, 162-166
	Y	C034	BJ	W0135	576B	24		31-31-20	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 213

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	C034	BJ	W0145	243B	24		31-31-20	ALL
	Y	C034	BJ	W0145	551B	24		31-35-12	ALL
	X	C037	BJ	W0135	658	22		31-31-18	ALL
	X	C037	BJ	W0145	121	22		31-31-18	ALL
	X	C038	BJ	W0135	253B	24		31-35-15	278-299
	X	C038	BJ	W0145	696B	24		31-35-15	278-299
	Y	C043	BJ	W0135	599B	24		34-61-16	ALL
	Y	C043	BJ	W0135	792B	24		34-61-24	ALL
	Y	C043	BJ	W0145	288B	24		34-61-24	ALL
	Y	C044	BJ	W0145	048	20		34-53-21	050-099, 155-199, 275-299
	Y	C044	BJ	W0145	059	22		34-53-21	050-099, 155-199, 275-299
	Y	C044	BJ	W0145	076	22		34-53-21	050-099, 155-199, 275-299
	X	C047	BJ	W0135	846R	24		34-61-15	050-099, 150-199, 275-276
	X	C047	BJ	W0145	596R	24		34-61-15	050-099, 150-199, 275-276
	X	C048	BJ	W0135	538R	24		31-31-22	050-099, 150-199, 275-276
	X	C048	BJ	W0135	778R	24		31-31-22	050-099, 150-199, 275-276
	Y	C049	BJ	W0135	589B	24		31-31-22	050-099, 150-199, 275-276
	Y	C049	BJ	W0135	590B	24		31-31-22	050-099, 150-199, 275-276
	Y	C049	BJ	W0135	825	20		31-31-22	050-099, 150-199, 275-276
	Y	C050	BJ	W0135	586B	24		31-31-22	050-099, 150-199, 275-276
	Y	C050	BJ	W0135	779B	24		31-31-22	050-099, 150-199, 275-276
	Y	C050	BJ	W0135	828	20		31-31-22	050-099, 150-199, 275-276
	Y	C053	BJ	W0145	375B	24		34-12-21	ALL
	Y	C053	BJ	W0145	377B	24		34-12-21	ALL
	Y	C053	BJ	W0145	378B	24		34-12-21	ALL
	Y	C054	BJ	W0145	191	22		34-61-24	ALL
	Y	C054	BJ	W0145	192	22		34-61-24	ALL
	Y	C054	BJ	W0145	193	22		34-22-26	ALL
	Y	C063	BJ	W0145	204B	24		27-32-21	050, 150, 152-199
	Y	C063	BJ	W0145	241B	24		22-32-11	ALL
	Y	C063	BJ	W0145	587B	24		34-61-26	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 214

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	C063	BJ	W0145	588B	24		34-61-26	ALL
	X	C068	BJ	W0145	568R	24		31-41-35	ALL
	X	C068	BJ	W0155	211R	24		31-41-35	ALL
	F	C070	2	W0135	592B	22		31-31-25	ALL
	F	C070	2	W0155	301Y	18		31-31-25	ALL
	R	C071	2	W0135	843	24		31-31-26	050-099, 150-199, 275-276
	Y	C073	BJ	W0135	600B	24		34-61-14	277-299
	R	C073	2	W0135	842	24		31-31-26	050-099, 150-199, 275-276
	Y	C073	BJ	W0145	223B	24		34-61-24	277-299
	Y	C073	BJ	W0145	271B	24		34-61-24	277-299
	Y	C075	BJ	W0135	600B	24		34-61-14	157, 167-199, 275-276
	Y	C075	BJ	W0145	223B	24		34-61-24	157, 167-199, 275-276
	Y	C075	BJ	W0145	224B	24		34-61-24	275-276
	Y	C075	BJ	W0145	271B	24		34-61-24	157, 167-199
	D	C076	2	W0145	098	24		34-61-25	050-099, 150-199, 275-276
	Y	C077	BJ	W0135	276B	24		34-61-14	157, 167-199, 275-276
	Y	C077	BJ	W0135	681B	24		34-61-14	157, 167-199, 275-276
	Y	C077	BJ	W0145	641B	24		34-61-24	157, 167-199, 275-276
	X	C083	BJ	W0135	846R	24		34-61-15	277-299
	X	C083	BJ	W0145	596R	24		34-61-15	277-299
	X	C084	BJ	W0135	538R	24		31-31-22	277-299
	X	C084	BJ	W0135	778R	24		31-31-22	277-299
	Y	C085	BJ	W0135	589B	24		31-31-22	277-299
	Y	C085	BJ	W0135	590B	24		31-31-22	277-299
	Y	C085	BJ	W0135	825	20		31-31-22	277-299
	Y	C086	BJ	W0135	586B	24		31-31-22	277-299
	Y	C086	BJ	W0135	779B	24		31-31-22	277-299
	Y	C086	BJ	W0135	828	20		31-31-22	277-299
	R	C087	2	W0135	043	22		31-31-18	278
	R	C087	2	W0135	057	22		31-31-18	278
	D	C088	2	W0145	663	24		34-61-26	278

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 215

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	D	C088	2	W0145	719	24		34-61-27	157, 167-199
	X	C089	BJ	W0135	05A	24		34-61-27	157, 167-199
	X	C089	**	W0145	717	24		34-61-27	157
	X	C089	%	W0145	717	24		34-61-27	167-199
	D	C089	2	W0145	719	24		34-61-27	275-299
	R	C090	2	W0135	843	24		31-31-26	277-299
	D	C090	2	W0145	897	22		34-12-62	050-099, 162-166
	R	C091	2	W0135	842	24		31-31-26	277-299
	D	C091	2	W0145	897	22		34-12-62	157, 167-199
	D	C092	2	W0145	663	24		34-61-26	050-099, 155-199, 275-277, 280-299
	D	C092	2	W0145	897	22		34-12-62	152
	D	C093	2	W0145	662	24		34-61-26	050-099, 155-199, 275-299
	D	C094	2	W0145	664	24		34-61-26	050-099, 155-199, 275-299
	R	C095	2	W0135	044	22		31-31-18	277-299
	R	C095	2	W0135	058	22		31-31-18	277-299
	D	C096	2	W0145	058	24		31-51-41	277-299
	D	C097	2	W0145	640	24		31-51-41	277-299
	Y	C101	BJ	W0135	577B	24		31-31-20	050-099, 150-199, 275-276
	R	C101	2	W0135	742	24		31-31-21	277-299
	R	C101	2	W0135	743	24		31-31-21	277-299
	Y	C101	BJ	W0145	249B	24		31-31-20	050-099, 150-199, 275-276
	Y	C101	BJ	W0145	552B	24		31-35-12	050-099, 150-199, 275-276
	R	C102	2	W0135	744	24		31-31-21	277-299
	R	C102	2	W0135	745	24		31-31-21	277-299
	R	C103	2	W0135	135	24		31-31-21	277-299
	Y	C103	BJ	W0135	575B	24		31-31-20	050-099, 150-199, 275-276
	R	C103	2	W0135	746	24		31-31-21	277-299
	Y	C103	BJ	W0145	502B	24		31-35-12	050-099, 150-199, 275-276
	Y	C103	BJ	W0155	209B	24		31-31-20	050-099, 150-199, 275-276
	R	C104	2	W0135	728	24		31-31-21	277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 216

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		<b>284T0384 (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	D	<b>DIODEBLOCK (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	F	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	G	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	H	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	R	<b>RESISTORBLOCK (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	Z	<b>BACM15C3C (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
	R	C104	2	W0135	729	24		31-31-21	277-299
	R	C105	2	W0135	725	24		31-31-21	277-299
	R	C105	2	W0135	726	24		31-31-21	277-299
	X	C105	BJ	W0135	819	24		31-31-26	050-099, 150-199, 275-276
	X	C105	BJ	W0145	659	24		31-31-26	050-099, 150-199, 275-276
	Y	C107	BJ	W0135	577B	24		31-31-20	277-299
	X	C107	BJ	W0135	823	24		31-31-26	050-099, 150-199, 275-276
	Y	C107	BJ	W0145	249B	24		31-31-20	277-299
	Y	C107	BJ	W0145	552B	24		31-35-12	277-299
	X	C107	BJ	W0145	657	24		31-31-26	050-099, 150-199, 275-276
	Y	C109	BJ	W0135	562B	24		31-31-20	050-099, 150-199, 275-276
	Y	C109	BJ	W0135	563B	24		31-31-20	050-099, 150-199, 275-276
	Y	C109	BJ	W0135	575B	24		31-31-20	277-299
	Y	C109	BJ	W0145	502B	24		31-35-12	277-299
	Y	C109	BJ	W0145	555B	24		31-35-12	050-099, 150-199, 275-276
	Y	C109	BJ	W0155	209B	24		31-31-20	277-299
	Y	C111	BJ	W0135	566B	24		31-31-20	050-099, 150-199, 275-276
	Y	C111	BJ	W0135	567B	24		31-31-20	050-099, 150-199, 275-276
	X	C111	BJ	W0135	819	24		31-31-26	277-299
	Y	C111	BJ	W0145	503B	24		31-35-12	050-099, 150-199, 275-276
	X	C111	BJ	W0145	659	24		31-31-26	277-299
	Y	C113	BJ	W0135	568B	24		31-31-20	050-099, 150-199, 275-276
	Y	C113	BJ	W0135	570B	24		31-31-20	050-099, 150-199, 275-276
	X	C113	BJ	W0135	823	24		31-31-26	277-299
	Y	C113	BJ	W0145	507B	24		31-35-12	050-099, 150-199, 275-276
	X	C113	BJ	W0145	657	24		31-31-26	277-299
	Y	C114	BJ	W0135	571B	24		31-31-20	050-099, 150-199, 275-276
	Y	C114	BJ	W0135	572B	24		31-31-20	050-099, 150-199, 275-276
	Y	C114	BJ	W0145	501B	24		31-35-12	050-099, 150-199, 275-276
	Y	C115	BJ	W0135	562B	24		31-31-20	277-299
	Y	C115	BJ	W0135	563B	24		31-31-20	277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 217

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	C115	BJ	W0145	555B	24		31-35-12	277-299
	R	C116	2	W0135	044	22		31-31-18	050-099, 150-199, 275-276
	R	C116	2	W0135	058	22		31-31-18	050-099, 150-199, 275-276
	R	C117	2	W0135	043	22		31-31-18	050-099, 150-199, 275-276
	R	C117	2	W0135	057	22		31-31-18	050-099, 150-199, 275-276
	Y	C117	BJ	W0135	566B	24		31-31-20	277-299
	Y	C117	BJ	W0135	567B	24		31-31-20	277-299
	Y	C117	BJ	W0145	503B	24		31-35-12	277-299
	X	C118	BJ	W0135	FRX			34-45-12	050-099, 150-199
	X	C118	BJ	W0145	675Z			34-45-12	050-099, 150-199, 275-276
	Y	C119	BJ	W0135	568B	24		31-31-20	277-299
	Y	C119	BJ	W0135	570B	24		31-31-20	277-299
	X	C119	BJ	W0135	FR3			34-45-12	050-099, 150-199
	Y	C119	BJ	W0145	507B	24		31-35-12	277-299
	X	C119	BJ	W0145	676Z			34-45-12	050-099, 150-199, 275-276
	R	C120	2	W0135	042	22		31-31-18	050-099, 150-199, 275-276
	R	C120	2	W0135	056	22		31-31-18	050-099, 150-199, 275-276
	Y	C120	BJ	W0135	571B	24		31-31-20	277-299
	Y	C120	BJ	W0135	572B	24		31-31-20	277-299
	Y	C120	BJ	W0145	501B	24		31-35-12	277-299
	R	C121	2	W0135	041	22		31-31-18	050-099, 150-199, 275-276
	R	C121	2	W0135	055	22		31-31-18	050-099, 150-199, 275-276
	R	C122	2	W0135	040	22		31-31-18	050-099, 150-199, 275-276
	R	C122	2	W0135	054	22		31-31-18	050-099, 150-199, 275-276
	R	C123	2	W0135	039	22		31-31-18	050-099, 150-199, 275-276
	R	C123	2	W0135	053	22		31-31-18	050-099, 150-199, 275-276
	X	C123	BJ	W0135	FRX			34-45-12	277-299
	X	C123	BJ	W0145	675Z			34-45-12	277-299
	X	C124	BJ	W0135	FR3			34-45-12	277-299
	X	C124	BJ	W0145	676Z			34-45-12	277-299
	D	C125	2	W0145	058	24		31-51-41	150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 218

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	D	C126	2	W0145	640	24		31-51-41	150-199, 275-276
	D	C127	2	W0135	008	24		31-31-11	050-099, 150-199, 275-276
	Y	C129	BJ	W0135	218B	24		31-31-11	ALL
	Y	C129	BJ	W0135	219B	24		31-31-11	ALL
	Y	C129	BJ	W0135	223B	24		31-31-11	ALL
	Y	C133	BJ	W0135	598B	24		34-61-16	050-099, 150-156, 162-166
	Y	C133	BJ	W0145	245B	24		34-22-28	ALL
	Y	C133	BJ	W0145	248B	24		34-61-25	ALL
	Y	C133	BJ	W0145	260B	24		31-35-13	ALL
	Y	C133	BJ	W0145	726B	24		34-61-25	157, 167-199
	Y	C135	BJ	W0145	267B	24		34-51-21	ALL
	Y	C135	BJ	W0145	285B	24		34-22-29	ALL
	Y	C135	BJ	W0155	210B	24		31-35-13	ALL
	Y	C136	BJ	W0135	01H	24		34-12-61	050-099
	Y	C136	BJ	W0145	857	24		34-12-22	050-099
	Y	C136	BJ	W0145	884	24		34-12-62	050-099
	Y	C139	BJ	W0135	107	24		31-31-12	ALL
	Y	C139	BJ	W0135	108	24		31-31-12	ALL
	Y	C139	BJ	W0145	159	24		31-31-12	ALL
	Y	C140	BJ	W0135	097	24		31-31-11	ALL
	Y	C140	BJ	W0135	834	24		31-35-11	ALL
	Y	C140	BJ	W0145	118	24		31-31-11	ALL
	X	C142	BJ	W0135	187	24		31-31-22	ALL
	X	C142	BJ	W0145	655	24		31-31-22	ALL
	Y	C143	BJ	W0135	230B	24		31-31-12	ALL
	Y	C143	BJ	W0135	579B	24		31-35-12	ALL
	Y	C143	BJ	W0145	516B	24		31-31-12	ALL
	Y	C144	BJ	W0135	275B	24		31-31-13	ALL
	Y	C144	BJ	W0135	580B	24		31-35-12	ALL
	Y	C144	BJ	W0135	793B	24		31-31-13	ALL
	Y	C144	BJ	W0145	574B	24		23-22-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 219

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	C145	BJ	W0135	228R	24		31-31-12	ALL
	X	C145	BJ	W0145	538R	24		31-31-12	ALL
	X	C149	BJ	W0135	151	24		31-31-18	ALL
	X	C149	BJ	W0145	183	24		31-31-18	ALL
	X	C151	BJ	W0135	155	24		31-31-18	ALL
	X	C151	BJ	W0145	180	24		31-31-18	ALL
	Y	C155	BJ	W0135	008	24		31-31-11	ALL
	Y	C155	BJ	W0135	013	24		31-31-13	ALL
	Y	C155	BJ	W0135	020	24		31-31-11	ALL
	X	C157	BJ	W0135	204R	24		34-61-23	ALL
	X	C157	BJ	W0145	215R	24		34-61-23	ALL
	X	C159	BJ	W0135	206R	24		34-61-23	ALL
	X	C159	BJ	W0145	217R	24		34-61-23	ALL
	X	C161	BJ	W0135	208R	24		34-61-11	ALL
	X	C161	BJ	W0145	206R	24		34-61-11	ALL
	X	C163	BJ	W0135	138	24		31-31-22	ALL
	X	C163	BJ	W0145	024	24		31-31-22	ALL
	Y	C167	BJ	W0145	01DB	24		34-12-62	ALL
	Y	C167	BJ	W0145	505B	24		34-12-22	ALL
	Y	C167	BJ	W0145	515B	24		34-12-22	ALL
	Y	C168	BJ	W0135	706	24		31-31-19	ALL
	Y	C168	BJ	W0145	197	24		34-61-26	ALL
	Y	C168	BJ	W0145	652	24		34-61-26	ALL
	X	C169	BJ	W0135	301Y	24		34-12-21	ALL
	X	C169	BJ	W0145	376Y	24		34-12-21	ALL
	Y	C179	BJ	W0135	840B	24		34-61-11	ALL
	Y	C179	BJ	W0145	299B	24		34-61-21	ALL
	Y	C179	BJ	W0145	685B	24		34-61-21	ALL
	Y	C180	BJ	W0135	598B	24		34-61-16	157, 167-199
	Y	C180	BJ	W0145	709B	24		34-61-25	157, 167-199
	Y	C180	BJ	W0145	726B	24		34-61-25	167-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 220

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		<b>284T0384 (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	D	<b>DIODEBLOCK (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	F	<b>BACM15C1A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	G	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	H	<b>BACM15C2A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	R	<b>RESISTORBLOCK (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
TB0145	Z	<b>BACM15C3C (continued)</b>					<b>SHELF/E02/03</b>		<b>ALL</b>
	D	C184	2	W0145	897	22		34-12-62	150-151, 153-156, 277-299
	Y	C185	BJ	W0135	01J	24		34-12-61	150-151, 153-199, 275-299
	Y	C185	BJ	W0145	750	24		34-12-62	150-151, 153-199, 275-299
	R	C187	2	W0135	082	24		31-31-17	ALL
	R	C187	2	W0145	115	24		31-31-17	ALL
	R	C188	2	W0135	083	24		31-31-17	ALL
	R	C188	2	W0145	116	24		31-31-17	155-157, 164-199, 277-299
	D	C189	2	W0145	721	24		34-61-27	157, 167-199, 275-299
	D	C190	2	W0145	098	24		34-61-25	277-299
	D	C190	2	W0145	897	22		34-12-62	275-276
	D	C191	2	W0135	008	24		31-31-11	277-299
	R	C192	2	W0135	043	22		31-31-18	277, 280-299
	R	C192	2	W0135	057	22		31-31-18	277, 280-299
	R	C193	2	W0135	042	22		31-31-18	277-299
	R	C193	2	W0135	056	22		31-31-18	277-299
	Y	C194	BJ	W0135	01J	24		34-12-61	050-099, 152
	R	C194	2	W0135	041	22		31-31-18	277-299
	R	C194	2	W0135	055	22		31-31-18	277-299
	Y	C194	BJ	W0145	750	24		34-12-62	050-099, 152
	R	C195	2	W0135	040	22		31-31-18	277-299
	R	C195	2	W0135	054	22		31-31-18	277-299
	R	C196	2	W0135	039	22		31-31-18	277-299
	R	C196	2	W0135	053	22		31-31-18	277-299
	D	C197	2	W0145	714	24		34-61-27	157, 167-199, 277-299
	X	D001	BJ	W0145	293B	24		23-51-12	050-099, 150-199, 275-276
	X	D001	BJ	W0145	302Y	24		23-51-12	050-099, 150-199, 275-276
	X	D007	BJ	W0145	293B	24		23-51-12	277-299
	X	D007	BJ	W0145	302Y	24		23-51-12	277-299
	X	D037	BJ	W0135	795	22		31-31-18	ALL
	X	D037	BJ	W0145	124	22		31-31-18	ALL
	X	D038	BJ	W0135	253R	24		31-35-15	278-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 221

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	D038	BJ	W0145	696R	24		31-35-15	278-299
	X	D047	BJ	W0135	846B	24		34-61-15	050-099, 150-199, 275-276
	X	D047	BJ	W0145	596B	24		34-61-15	050-099, 150-199, 275-276
	X	D048	BJ	W0135	586R	24		31-31-22	050-099, 150-199, 275-276
	X	D048	BJ	W0135	779R	24		31-31-22	050-099, 150-199, 275-276
	X	D068	BJ	W0145	568B	24		31-41-35	ALL
	X	D068	BJ	W0155	211B	24		31-41-35	ALL
	X	D083	BJ	W0135	846B	24		34-61-15	277-299
	X	D083	BJ	W0145	596B	24		34-61-15	277-299
	X	D084	BJ	W0135	586R	24		31-31-22	277-299
	X	D084	BJ	W0135	779R	24		31-31-22	277-299
	X	D105	BJ	W0135	820	24		31-31-26	050-099, 150-199, 275-276
	X	D105	BJ	W0145	660	24		31-31-26	050-099, 150-199, 275-276
	X	D111	BJ	W0135	820	24		31-31-26	277-299
	X	D111	BJ	W0145	660	24		31-31-26	277-299
	X	D141	BJ	W0135	163	24		31-31-14	ALL
	X	D141	BJ	W0145	566	24		31-31-14	ALL
	X	D142	BJ	W0135	081	24		31-31-17	ALL
	X	D142	BJ	W0145	112	24		31-31-17	ALL
	X	D145	BJ	W0135	228B	24		31-31-12	ALL
	X	D145	BJ	W0145	538B	24		31-31-12	ALL
	X	D149	BJ	W0135	152	24		31-31-18	ALL
	X	D149	BJ	W0145	184	24		31-31-18	ALL
	X	D151	BJ	W0135	156	24		31-31-18	ALL
	X	D151	BJ	W0145	185	24		31-31-18	ALL
	X	D157	BJ	W0135	204B	24		34-61-23	ALL
	X	D157	BJ	W0145	215B	24		34-61-23	ALL
	X	D159	BJ	W0135	206B	24		34-61-23	ALL
	X	D159	BJ	W0145	217B	24		34-61-23	ALL
	X	D161	BJ	W0135	208B	24		34-61-11	ALL
	X	D161	BJ	W0145	206B	24		34-61-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 222

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	D163	BJ	W0135	139	24		31-31-22	ALL
	X	D163	BJ	W0145	046	24		31-31-22	ALL
	X	D169	BJ	W0135	809	24		34-61-25	ALL
	X	D169	BJ	W0145	666	24		34-61-25	ALL
	X	DED		W0135	005Z			31-31-11	ALL
	X	DED		W0135	079Z			31-31-17	ALL
	X	DED		W0135	080Z			31-31-17	ALL
	X	DED		W0135	081Z			31-31-17	ALL
	R	DED		W0135	082Z			31-31-17	ALL
	R	DED		W0135	083Z			31-31-17	ALL
	Y	DED		W0135	097Z			31-31-11	ALL
	X	DED		W0135	192Z			31-31-14	ALL
	R	DED		W0135	302Z			31-31-19	ALL
	R	DED		W0135	305Z			31-31-19	ALL
	Y	DED		W0135	855Z			34-61-24	050-099, 155-199, 276-299
	X	DED		W0145	011Z			34-61-23	ALL
	X	DED		W0145	012Z			34-61-23	ALL
	Y	DED		W0145	048Z			34-53-21	050-099, 155-199, 275-299
	G	DED		W0145	048Z			34-53-21	150-154
	Z	DED		W0145	105Z			31-31-12	ALL
	Z	DED		W0145	106Z			31-31-11	ALL
	Y	DED		W0145	107Z			31-31-11	ALL
	Z	DED		W0145	117Z			31-31-11	ALL
	Z	DED		W0145	158Z			31-31-12	ALL
	Y	DED		W0145	223Z			34-61-24	157, 167-199
	Y	DED		W0145	299Z			34-61-21	ALL
	Z	DED		W0145	514Z			34-12-22	ALL
	Y	DED		W0145	586Z			34-12-22	ALL
	Y	DED		W0145	726Z			34-61-25	157, 167-199
	Y	DED		W0145	801Z			34-12-21	ALL
	X	DED		W0145	827Z			34-12-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 223

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	DED		W0145	830Z			34-12-21	ALL
	Z	DED		W0145	831Z			34-12-21	ALL
	Z	DED		W0145	832Z			34-12-21	ALL
	Y	DED		W0145	834Z			34-12-21	ALL
	X	REF		W0135	203	20		34-61-23	050-099, 150-199, 275-276
	X	REF		W0135	203Z			34-61-23	050-099, 150-199, 275-276
	X	REF		W0135	204	20		34-61-23	050-099, 150-199, 275-276
	X	REF		W0135	204Z			34-61-23	050-099, 150-199, 275-276
	X	REF		W0135	205	20		34-61-23	050-099, 150-199, 275-276
	X	REF		W0135	205Z			34-61-23	050-099, 150-199, 275-276
	X	REF		W0135	206	20		34-61-23	050-099, 150-199, 275-276
	X	REF		W0135	206Z			34-61-23	050-099, 150-199, 275-276
	X	REF		W0135	208	20		34-61-11	050-099, 150-199, 275-276
	X	REF		W0135	208Z			34-61-11	050-099, 150-199, 275-276
	X	REF		W0135	209	20		34-61-11	050-099, 150-199, 275-276
	X	REF		W0135	209Z			34-61-11	050-099, 150-199, 275-276
	X	REF		W0135	226	20		31-31-14	050-099, 152-199, 275-299
	X	REF		W0135	226Z			31-31-14	050-099, 152-199, 275-299
	Y	REF		W0135	230	20		31-31-12	050-099, 152-199, 275-299
	Y	REF		W0135	230Z			31-31-12	050-099, 152-199, 275-299
	Y	REF		W0135	275	20		31-31-13	050-099, 152-199, 275-276
	Y	REF		W0135	275Z			31-31-13	050-099, 152-199, 275-276
	Y	REF		W0135	276	20		34-61-14	157, 167-199, 275-299
	Y	REF		W0135	276Z			34-61-14	157, 167-199, 275-299
	X	REF		W0135	299Z			34-45-12	153-154
	Y	REF		W0135	525	20		31-31-20	150-156, 162-166, 280-299
	Z	REF		W0135	525	20		31-31-20	157, 167-199, 275-278
	Y	REF		W0135	525Z			31-31-20	150-156, 162-166, 280-299
	Z	REF		W0135	525Z			31-31-20	157, 167-199, 275-278
	Y	REF		W0135	579	20		31-35-12	050-099, 152-199, 275-299
	Y	REF		W0135	579Z			31-35-12	050-099, 152-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 224

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Y	REF		W0135	580	20		31-35-12	050-099, 152-199, 275-276
	Y	REF		W0135	580Z			31-35-12	050-099, 152-199, 275-276
	Z	REF		W0135	597	20		34-61-16	050-099, 150-199, 275-276
	Z	REF		W0135	597Z			34-61-16	050-099, 150-199, 275-276
	Y	REF		W0135	598	20		34-61-16	157, 167-199, 275-299
	Y	REF		W0135	598Z			34-61-16	157, 167-199, 275-299
	Y	REF		W0135	599	20		34-61-16	050-099, 152-199, 275-299
	Y	REF		W0135	599Z			34-61-16	050-099, 152-199, 275-299
	Y	REF		W0135	600	20		34-61-14	157, 167-199, 275-276
	Y	REF		W0135	600Z			34-61-14	157, 167-199, 275-276
	Y	REF		W0135	681	20		34-61-14	157, 167-199, 275-299
	Y	REF		W0135	681Z			34-61-14	157, 167-199, 275-299
	Y	REF		W0135	792	20		34-61-24	050-099, 152-199, 275-299
	Y	REF		W0135	792Z			34-61-24	050-099, 152-199, 275-299
	Y	REF		W0135	793	20		31-31-13	050-099, 152-199, 275-276
	Y	REF		W0135	793Z			31-31-13	050-099, 152-199, 275-276
	X	REF		W0135	833Z			34-45-12	050-099, 150-199, 277-299
	Y	REF		W0135	840	20		34-61-11	050-099, 151-152, 154, 156-157, 275-276
	Y	REF		W0135	840Z			34-61-11	050-099, 151-152, 154, 156-157, 275-276
	X	REF		W0135	857Z			34-45-12	050-099, 150-152, 155-199, 277-299
	X	REF		W0135	FR3			34-45-12	050-099, 150-199, 277-299
	X	REF		W0135	FRL			34-45-12	050-099, 150-199, 277-299
	X	REF		W0135	FRV			34-45-12	050-099, 150-199, 277-299
	X	REF		W0135	FRX			34-45-12	050-099, 150-199, 277-299
	X	REF		W0145	201	20		34-61-11	050-099, 150-199, 275-276
	X	REF		W0145	201Z			34-61-11	050-099, 150-199, 275-276
	X	REF		W0145	206	20		34-61-11	050-099, 150-199, 275-276
	X	REF		W0145	206Z			34-61-11	050-099, 150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 225

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	REF		W0145	213	20		34-61-23	050-099, 150-199, 275-276
	X	REF		W0145	213Z			34-61-23	050-099, 150-199, 275-276
	X	REF		W0145	214	20		34-61-23	050-099, 150-199, 275-276
	X	REF		W0145	214Z			34-61-23	050-099, 150-199, 275-276
	X	REF		W0145	215	20		34-61-23	050-099, 150-199, 275-276
	X	REF		W0145	215Z			34-61-23	050-099, 150-199, 275-276
	X	REF		W0145	217	20		34-61-23	050-099, 150-199, 275-276
	X	REF		W0145	217Z			34-61-23	050-099, 150-199, 275-276
	Z	REF		W0145	221	20		34-61-22	050-099, 150-199, 275-276
	Z	REF		W0145	221Z			34-61-22	050-099, 150-199, 275-276
	Y	REF		W0145	223	20		34-61-24	275-276
	Y	REF		W0145	223Z			34-61-24	275-276
	Y	REF		W0145	224	20		34-61-24	275-276
	Y	REF		W0145	224Z			34-61-24	275-276
	Y	REF		W0145	241	20		22-32-11	050-099, 150-199, 275-276
	Y	REF		W0145	241Z			22-32-11	050-099, 150-199, 275-276
	Z	REF		W0145	264	20		34-51-21	277-299
	Z	REF		W0145	264Z			34-51-21	277-299
	Y	REF		W0145	271	20		34-61-24	157, 167-199
	Y	REF		W0145	271Z			34-61-24	157, 167-199
	Y	REF		W0145	281	20		34-55-21	050-099, 150-156, 162-166
	Z	REF		W0145	281	20		34-55-21	157, 167-199, 275-299
	Y	REF		W0145	281Z			34-55-21	050-099, 150-156, 162-166
	Z	REF		W0145	281Z			34-55-21	157, 167-199, 275-299
	Y	REF		W0145	284	20		34-22-29	050-099, 150-156, 162-166
	Z	REF		W0145	284	20		34-22-29	157, 167-199, 275-299
	Y	REF		W0145	284Z			34-22-29	050-099, 150-156, 162-166
	Z	REF		W0145	284Z			34-22-29	157, 167-199, 275-299
	Y	REF		W0145	288	20		34-61-24	050-099, 152-199, 275-299
	Y	REF		W0145	288Z			34-61-24	050-099, 152-199, 275-299
	Z	REF		W0145	291	20		34-55-21	277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 226

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	Z	REF		W0145	291Z			34-55-21	277-299
	Z	REF		W0145	295	20		34-61-25	050-099, 150-199, 275-276
	Z	REF		W0145	295Z			34-61-25	050-099, 150-199, 275-276
	Z	REF		W0145	296	20		34-61-25	277-299
	Z	REF		W0145	296Z			34-61-25	277-299
	Y	REF		W0145	505	20		34-12-22	050-099, 150-199, 275-276
	Y	REF		W0145	505Z			34-12-22	050-099, 150-199, 275-276
	Z	REF		W0145	513	20		34-12-22	050-099, 150-199, 275-276
	Z	REF		W0145	513Z			34-12-22	050-099, 150-199, 275-276
	Y	REF		W0145	515	20		34-12-22	050-099, 150-199, 275-276
	Y	REF		W0145	515Z			34-12-22	050-099, 150-199, 275-276
	Y	REF		W0145	516	20		31-31-12	050-099, 152-199, 275-299
	Y	REF		W0145	516Z			31-31-12	050-099, 152-199, 275-299
	Z	REF		W0145	525	20		34-21-21	050-099, 150-199
	Y	REF		W0145	525	20		34-21-21	275-276
	Z	REF		W0145	525Z			34-21-21	050-099, 150-199
	Y	REF		W0145	525Z			34-21-21	275-276
	X	REF		W0145	529	20		31-31-14	050-099, 152-199, 275-299
	X	REF		W0145	529Z			31-31-14	050-099, 152-199, 275-299
	Z	REF		W0145	540	20		34-61-25	050-099, 150-199, 275-276
	Z	REF		W0145	540Z			34-61-25	050-099, 150-199, 275-276
	Z	REF		W0145	544	20		31-41-33	050-099, 152-199, 275-276
	Z	REF		W0145	544Z			31-41-33	050-099, 152-199, 275-276
	Y	REF		W0145	554	20		31-35-12	050-099, 150-156, 162-166, 280-299
	Z	REF		W0145	554	20		31-35-12	157, 167-199, 275-278
	Y	REF		W0145	554Z			31-35-12	050-099, 150-156, 162-166, 280-299
	Z	REF		W0145	554Z			31-35-12	157, 167-199, 275-278
	X	REF		W0145	568	20		31-41-35	050-099, 150-199, 275-276
	X	REF		W0145	568Z			31-41-35	050-099, 150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 227

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	REF		W0145	570	20		28-41-11	050-099, 150-199, 275-276
	X	REF		W0145	570Z			28-41-11	050-099, 150-199, 275-276
	Y	REF		W0145	571	20		27-11-12	050-099
	Z	REF		W0145	571	20		27-11-12	150-199, 275-276
	Y	REF		W0145	571Z			27-11-12	050-099
	Z	REF		W0145	571Z			27-11-12	150-199, 275-276
	Z	REF		W0145	572	20		34-13-21	050-099, 150-199, 275-276
	Z	REF		W0145	572Z			34-13-21	050-099, 150-199, 275-276
	Z	REF		W0145	573	20		34-21-31	050-099, 152-199, 275-276
	Z	REF		W0145	573Z			34-21-31	050-099, 152-199, 275-276
	Y	REF		W0145	587	20		34-61-26	050-099, 150-199, 275-276
	Y	REF		W0145	587Z			34-61-26	050-099, 150-199, 275-276
	Y	REF		W0145	588	20		34-61-26	050-099, 150-199, 275-276
	Y	REF		W0145	588Z			34-61-26	050-099, 150-199, 275-276
	Z	REF		W0145	598	20		23-25-13	150, 153-199
	Z	REF		W0145	598Z			23-25-13	150, 153-199
	Y	REF		W0145	641	20		34-61-24	157, 167-199, 275-299
	Y	REF		W0145	641Z			34-61-24	157, 167-199, 275-299
	Y	REF		W0145	704	20		34-45-14	050-099, 153-156, 162-166
	Z	REF		W0145	704	20		34-45-14	275-276
	Y	REF		W0145	704Z			34-45-14	050-099, 153-156, 162-166
	Z	REF		W0145	704Z			34-45-14	275-276
	Y	REF		W0145	709	20		34-61-25	157, 167-199, 275-299
	Y	REF		W0145	709Z			34-61-25	157, 167-199, 275-299
	Z	REF		W0145	715	20		34-61-27	157, 167-199, 275-299
	Z	REF		W0145	715Z			34-61-27	157, 167-199, 275-299
	Y	REF		W0145	716	20		34-61-27	157, 167-199
	Z	REF		W0145	716	20		34-61-27	275-299
	Y	REF		W0145	716Z			34-61-27	157, 167-199
	Z	REF		W0145	716Z			34-61-27	275-299
	X	REF		W0155	211	20		31-41-35	050-099, 150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 228

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0145		284T0384 (continued)					SHELF/E02/03		ALL
TB0145	D	DIODEBLOCK (continued)					SHELF/E02/03		ALL
TB0145	F	BACM15C1A (continued)					SHELF/E02/03		ALL
TB0145	G	BACM15C1B (continued)					SHELF/E02/03		ALL
TB0145	H	BACM15C2A (continued)					SHELF/E02/03		ALL
TB0145	R	RESISTORBLOCK (continued)					SHELF/E02/03		ALL
TB0145	X	BACM15C3A (continued)					SHELF/E02/03		ALL
TB0145	Y	BACM15C3B (continued)					SHELF/E02/03		ALL
TB0145	Z	BACM15C3C (continued)					SHELF/E02/03		ALL
	X	REF		W0155	211Z			31-41-35	050-099, 150-199, 275-276
	X	REF		W0155	212	20		28-41-11	050-099, 150-199, 275-276
	X	REF		W0155	212Z			28-41-11	050-099, 150-199, 275-276
	F	REF		W0155	301	20		31-31-25	050-099, 150-199, 275-276
	F	REF		W0155	301Z			31-31-25	050-099, 150-199, 275-276
TB0146		BACT44B1350U					P019-00/ /		050-099
TB0146		BACT44B1550U					P019-00/ /		150-199, 275-299
TB0146	F	BACM15C1A					P019-00/ /		ALL
TB0146	G	BACM15C1B					P019-00/ /		ALL
TB0146	H	BACM15C2A					P019-00/ /		ALL
TB0146	X	BACM15C3A					P019-00/ /		ALL
TB0146	Y	BACM15C3B					P019-00/ /		ALL
TB0146	Z	BACM15C3C					P019-00/ /		ALL
	H	1	2	W1060	01V	18		33-22-31	280-299
	H	1	2	W1060	031	20		33-22-11	280-299
	H	1	2	W1060	528	20		33-22-11	280-299
	H	1	2	W1104	832	20		33-22-31	280-299
	H	1	2	W1110	076	18		33-22-31	280-299
	Z	13	BJ	W1058	106	20		33-24-11	150-199
	Z	13	BJ	W1060	068	22		33-24-11	150-199
	Z	13	BJ	W1060	071	22		33-24-11	150-199
	Z	13	BJ	W1060	784	20		33-24-11	150-199
	Z	13	BJ	W1060	788	20		33-24-11	150-199
	Z	13	BJ	W1102	052	22		33-24-11	150-199
	Z	14	BJ	W1058	107	20		33-24-11	150-199
	Z	14	BJ	W1060	072	22		33-24-11	150-199
	Z	14	BJ	W1060	088	22		33-24-11	150-199
	Z	14	BJ	W1060	783	20		33-24-11	150-199
	Z	14	BJ	W1060	787	20		33-24-11	150-199
	Z	14	BJ	W1102	051	22		33-24-11	150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 229

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Z	19	BJ	W1060	021	22		33-24-11	162-199
	Z	19	BJ	W1060	070	22		33-24-11	050-099
	Z	19	BJ	W1060	070	20		33-24-11	150-199, 275-299
	Z	19	BJ	W1060	078	22		33-24-11	050-099
	Z	19	BJ	W1060	078	20		33-24-11	150-199, 275-299
	Z	19	BJ	W1060	085	22		33-24-11	050-099
	Z	19	BJ	W1060	085	20		33-24-11	150-199, 275-299
	Z	19	BJ	W1060	087	22		33-24-11	050-099
	Z	19	BJ	W1060	087	20		33-24-11	150-199, 275-299
	Z	19	BJ	W1060	592	20		33-24-11	275-299
	Z	19	BJ	W1060	715	20		33-24-11	275-299
	Z	19	BJ	W1060	783	20		33-24-11	050-099
	Z	19	BJ	W1060	832	22		33-24-11	050-099
	Z	19	BJ	W1104	770	20		33-24-11	275-299
	Z	19	BJ	W1110	078	20		33-24-11	275-299
	Z	20	BJ	W1058	022	20		33-24-11	275-299
	Z	20	BJ	W1060	022	22		33-24-11	162-199
	Z	20	BJ	W1060	069	22		33-24-11	050-099
	Z	20	BJ	W1060	069	20		33-24-11	150-199, 275-299
	Z	20	BJ	W1060	076	22		33-24-11	050-099
	Z	20	BJ	W1060	076	20		33-24-11	150-199, 275-299
	Z	20	BJ	W1060	077	22		33-24-11	050-099
	Z	20	BJ	W1060	077	20		33-24-11	150-199, 275-299
	Z	20	BJ	W1060	086	22		33-24-11	050-099
	Z	20	BJ	W1060	086	20		33-24-11	150-199, 275-299
	Z	20	BJ	W1060	534	24		31-31-26	ALL
	Z	20	BJ	W1060	712	22		33-24-11	050-099
	Z	20	BJ	W1060	712	20		33-24-11	275-299
	Z	20	BJ	W1060	784	20		33-24-11	050-099
	Z	20	BJ	W1060	812	20		33-24-11	275-299
	H	22	2	W1058	017	24		33-24-11	ALL
	H	22	2	W1060	065	24		33-24-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 230

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		BACT44B1350U (continued)					P019-00/ /		050-099
TB0146		BACT44B1550U (continued)					P019-00/ /		150-199, 275-299
TB0146	F	BACM15C1A (continued)					P019-00/ /		ALL
TB0146	G	BACM15C1B (continued)					P019-00/ /		ALL
TB0146	H	BACM15C2A (continued)					P019-00/ /		ALL
TB0146	X	BACM15C3A (continued)					P019-00/ /		ALL
TB0146	Y	BACM15C3B (continued)					P019-00/ /		ALL
TB0146	Z	BACM15C3C (continued)					P019-00/ /		ALL
	H	22	2	W1060	083	24		33-24-11	ALL
	H	22	2	W1060	093	24		33-24-11	ALL
	H	22	2	W1060	506	22		23-31-11	ALL
	H	22	2	W1060	508	22		23-31-11	ALL
	Z	25	BJ	W1104	057	20		33-21-31	ALL
	Z	25	BJ	W1104	059	20		33-21-31	ALL
	Z	25	BJ	W1104	060	20		33-21-31	ALL
	Z	25	BJ	W1104	061	20		33-21-31	166
	Z	25	BJ	W1104	062	20		33-21-31	ALL
	Z	25	BJ	W1104	095	20		33-21-31	150-199, 275-299
	Z	25	BJ	W1104	096	20		33-21-31	ALL
	Z	25	BJ	W1104	097	20		33-21-31	150-165, 167-199, 275-299
	Z	26	BJ	W1104	127	20		33-27-11	ALL
	Z	26	BJ	W1104	130	20		33-27-11	ALL
	Z	26	BJ	W1104	146	20		33-21-31	ALL
	Z	26	BJ	W1104	609	20		33-21-31	050-099
	Z	26	BJ	W1104	610	20		33-21-31	050-099
	Z	29	BJ	W1060	001	24		33-21-11	ALL
	Z	29	BJ	W1104	003	24		33-21-11	ALL
	Z	29	BJ	W1104	005	24		33-21-11	ALL
	Z	29	BJ	W1104	009	24		33-21-11	ALL
	Z	29	BJ	W1104	013	24		33-21-11	275-299
	Z	29	BJ	W1104	034	24		33-21-11	275-299
	Z	30	BJ	W1104	001	20		33-21-11	ALL
	Z	30	BJ	W1104	002	20		33-21-11	ALL
	Z	30	BJ	W1104	008	20		33-21-11	ALL
	Z	30	BJ	W1104	012	20		33-21-11	275-299
	Z	30	BJ	W1104	033	20		33-21-11	275-299
	Z	30	BJ	W1104	165	20		33-21-11	050-099, 150-199
	Z	30	BJ	W1104	598	20		33-21-11	050-099, 150-199
	G	32	2	W1060	031	20		33-22-11	275-278
	G	32	2	W1060	528	20		33-22-11	275-278

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 231

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	G	32	2	W1110	076	18		33-22-31	275-278
	Z	33	BJ	W1060	004	22		33-21-21	050-099
	Z	33	BJ	W1060	004	20		33-21-21	150-199, 275-299
	Z	33	BJ	W1060	005	22		33-21-21	ALL
	Z	33	BJ	W1060	007	22		33-21-21	ALL
	Z	33	BJ	W1060	010	22		33-21-21	050-099, 150-199
	Z	33	BJ	W1060	010	24		33-21-21	275-299
	Z	33	BJ	W1060	01U	22		33-21-21	280-299
	Z	33	BJ	W1060	054	22		33-22-41	150-199, 275-299
	Z	33	BJ	W1060	621	22		33-21-21	162-199
	Z	33	BJ	W1060	624	22		33-21-21	050-099, 150-157, 275-278
	Z	33	BJ	W1060	630	22		33-22-41	150-199, 275-299
	Z	33	BJ	W1104	784	20		33-27-11	050-099
	Z	33	BJ	W1104	786	20		33-27-11	050-099
	Z	33	BJ	W1110	085	22		33-51-11	ALL
	Z	34	BJ	W1060	008	22		33-21-21	162-199
	Z	34	BJ	W1060	019	22		33-21-21	162-199
	Z	34	BJ	W1060	020	22		33-21-21	162-199
	Z	34	BJ	W1060	054	22		33-22-41	050-099
	Z	34	BJ	W1060	621	22		33-21-21	162-199
	Z	34	BJ	W1060	624	22		33-21-21	050-099
	Z	34	BJ	W1060	630	22		33-22-41	050-099
	Z	34	BJ	W1060	680	22		33-21-21	050-099
	Z	34	BJ	W1060	682	22		33-21-21	050-099
	Z	34	BJ	W1060	686	22		33-21-21	050-099
	Z	34	BJ	W1060	770	22		33-22-41	050-099
	Z	34	BJ	W1060	821	22		33-21-21	050-099, 162-199
	Z	35	BJ	W1058	005	20		33-26-21	275-299
	Z	35	BJ	W1058	007	20		33-26-21	050-099, 150-199
	Z	35	BJ	W1058	007	22		33-26-21	275-299
	Z	35	BJ	W1058	024	20		33-26-11	275-299
	Z	35	BJ	W1058	605	22		33-26-21	275-278

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 232

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	F	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	G	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	H	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	X	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	Y	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	Z	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Z	35	BJ	W1058	618	22		33-26-21	280-299
	Z	35	BJ	W1060	099	20		33-26-21	050-099, 150-199
	Z	35	BJ	W1102	013	20		33-26-21	ALL
	Z	35	BJ	W1102	034	20		33-26-11	150-199, 275-299
	Z	35	BJ	W1104	032	20		33-26-11	050-099
	Z	35	BJ	W1104	032	22		33-26-11	150-199
	Z	35	BJ	W1104	032	20		33-26-21	275-299
	Z	35	BJ	W1104	121	22		33-26-21	275-278
	Z	35	BJ	W1104	787	20		33-26-21	050-099
	Z	35	BJ	W1104	816	20		33-26-11	050-099
	Z	35	BJ	W1104	873	22		33-26-21	280-299
	Z	36	BJ	W1058	011	22		33-26-11	ALL
	Z	36	BJ	W1060	520	20		33-26-11	ALL
	Z	36	BJ	W1102	012	22		33-26-11	050-099, 275-299
	Z	36	BJ	W1104	115	20		33-26-11	ALL
	Z	36	BJ	W1104	592	22		33-26-11	275-299
	Z	36	BJ	W1104	593	22		33-26-11	150-199
	Z	39	BJ	W1060	059	22		33-51-11	ALL
	Z	39	BJ	W1060	107	22		33-51-11	ALL
	Z	39	BJ	W1060	120	22		33-51-11	ALL
	Z	39	BJ	W1060	122	22		33-51-11	ALL
	Z	39	BJ	W1060	128	22		33-51-11	ALL
	G	4	2	W1058	012	16		38-13-11	150-199, 275-299
	G	4	2	W1102	014	16		38-13-11	050-099, 275-299
	G	4	2	W1102	015	16		38-13-11	ALL
	G	4	2	W1102	022	16		38-13-11	ALL
	Z	40	BJ	W1060	142	20		33-51-21	ALL
	Z	40	BJ	W1060	143	20		33-51-21	ALL
	Z	40	BJ	W1060	566	22		33-51-11	ALL
	Z	40	BJ	W1060	642	20		33-51-11	ALL
	Z	40	BJ	W1110	091	20		33-51-11	ALL
	Y	A002	BJ	W1060	629	22		33-22-41	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 233

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Y	A002	BJ	W1104	735	22		33-22-41	050-099, 150-199
	F	A003	2	W1058	015	20		33-44-11	ALL
	F	A003	2	W1104	119	20		33-44-11	ALL
	Y	A005	BJ	W1058	002	22		33-25-11	ALL
	Y	A005	BJ	W1058	003	22		33-25-11	ALL
	Y	A005	BJ	W1102	009	22		33-25-11	ALL
	Y	A005	BJ	W1104	590	22		33-25-11	275-299
	Y	A006	BJ	W1058	009	22		33-26-11	050-099, 275-299
	Y	A006	BJ	W1058	010	22		33-26-11	050-099, 275-299
	Y	A006	BJ	W1102	011	22		33-26-11	050-099, 275-299
	Y	A006	BJ	W1102	023	22		33-26-11	275-299
	Y	A006	BJ	W1104	815	20		33-26-11	050-099
	X	A007	BJ	W1058	031	20		33-26-21	162-199
	X	A007	BJ	W1058	038	20		33-26-21	150-157
	X	A007	BJ	W1058	038	22		33-26-21	275-278
	X	A007	BJ	W1060	620	20		33-26-21	150-157
	X	A007	BJ	W1060	620	22		33-26-21	275-278
	X	A007	BJ	W1102	105	20		33-26-21	162-199
	X	A009	BJ	W1102	078	20		33-26-21	050-099
	X	A009	BJ	W1104	793	20		33-26-21	050-099
	Y	A011	BJ	W1058	104	20		25-42-11	ALL
	Y	A011	BJ	W1102	102	20		25-42-11	ALL
	Y	A011	BJ	W1102	104	20		25-42-11	ALL
	Y	A011	BJ	W1104	727	20		25-42-11	ALL
	Y	A012	BJ	W1060	017	22		33-21-21	050-099, 150-199
	Y	A012	BJ	W1060	018	22		33-21-21	050-099, 150-199
	Y	A012	BJ	W1060	026	22		33-21-21	050-099
	Y	A012	BJ	W1060	781	22		33-21-21	050-099, 150-199
	Y	A014	BJ	W1060	01W	20		33-24-11	280-299
	Y	A014	BJ	W1060	710	20		33-24-11	280-299
	Y	A014	BJ	W1060	793	20		33-24-11	280-299
	Y	A015	BJ	W1060	063	22		33-24-11	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 234

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	F	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	G	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	H	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	X	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	Y	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	Z	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Y	A015	BJ	W1060	063	20		33-24-11	150-199, 275-299
	Y	A015	BJ	W1060	081	22		33-24-11	050-099
	Y	A015	BJ	W1060	081	20		33-24-11	150-199, 275-299
	Y	A015	BJ	W1060	082	22		33-24-11	050-099
	Y	A015	BJ	W1060	082	20		33-24-11	150-199, 275-299
	Y	A016	BJ	W1060	075	24		33-24-11	ALL
	Y	A016	BJ	W1060	084	24		33-24-11	ALL
	Y	A016	BJ	W1060	090	24		33-24-11	ALL
	Y	A017	BJ	W1060	092	24		33-24-11	ALL
	Y	A017	BJ	W1060	095	20		33-24-11	ALL
	Y	A017	BJ	W1060	096	24		33-24-11	ALL
	Y	A018	BJ	W1060	051	22		33-22-41	150-199
	Y	A018	BJ	W1060	517	22		33-22-32	050-099, 150-199
	Y	A018	BJ	W1060	518	22		33-22-41	050-099, 150-199
	Y	A018	BJ	W1060	700	22		33-22-41	050-099
	F	A024	2	W1060	768	22		33-22-41	050-099, 150-199
	F	A024	2	W1104	639	22		33-22-41	050-099, 150-199
	Y	A027	BJ	W1104	007	20		33-21-11	150-199
	Y	A027	BJ	W1104	042	20		33-21-11	150-199
	Y	A027	BJ	W1104	122	20		33-21-11	150-199
	Y	A028	BJ	W1058	005	20		33-26-21	050-099, 150-199
	Y	A028	BJ	W1058	105	20		33-26-11	050-099, 150-199
	Y	A028	BJ	W1060	099	20		33-26-21	275-299
	Y	A028	BJ	W1060	581	20		33-26-21	ALL
	Y	A028	BJ	W1102	034	20		33-26-11	050-099
	Y	A028	BJ	W1104	594	20		33-26-11	275-299
	Y	A032	BJ	W1060	031	24		33-21-31	155-157, 166-199
	Y	A032	BJ	W1060	502	24		33-21-31	155-157, 166-199
	Y	A032	BJ	W1060	528	24		33-21-31	155-157, 166-199
	Y	A032	BJ	W1060	532	20		33-21-31	050-099
	Y	A032	BJ	W1060	687	20		33-21-31	155-157, 166-199
	Y	A032	BJ	W1060	742	24		33-21-31	050-099, 150-154, 162-165

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 235

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Y	A032	BJ	W1060	743	24		33-21-31	050-099, 150-154, 162-165
	Y	A032	BJ	W1060	744	24		33-21-31	050-099, 150-154, 162-165
	Y	A032	BJ	W1104	832	20		33-21-31	150-154, 162-165
	Y	A037	BJ	W1058	041	20		38-32-12	050-099, 150-156, 162-165, 275-276
	Y	A037	BJ	W1058	041	20		38-32-16	157, 166-199, 277-299
	Y	A037	BJ	W1102	036	20		38-32-12	050-099, 150-156, 162-165, 275-276
	Y	A037	BJ	W1102	039	20		38-32-12	050-099, 150-156, 162-165, 275-276
	Y	A037	BJ	W1102	039	20		38-32-16	157, 166-199, 277-299
	Y	A037	BJ	W1102	040	20		38-32-12	050-099, 150-156, 162-165, 275-276
	Y	A037	BJ	W1102	040	20		38-32-16	157, 166-199, 277-299
	Y	A038	BJ	W1060	630	22		33-22-41	150-199
	Y	A038	BJ	W1060	752	22		33-22-41	150-199
	Y	A038	BJ	W1060	770	22		33-22-41	150-199
	Y	A043	BJ	W1060	519	22		33-22-21	280-299
	Y	A043	BJ	W1060	849	22		33-22-21	162-199
	Y	A043	BJ	W1060	850	22		33-22-21	162-199
	Y	A043	BJ	W1060	876	22		33-22-21	162-199
	Y	A043	BJ	W1060	901	22		33-22-21	162-199
	Y	A043	BJ	W1104	879	22		33-22-21	280-299
	Y	A044	BJ	W1060	858	22		21-66-21	050-099, 162-199
	Y	A044	BJ	W1060	859	22		21-66-21	050-099, 162-199
	Y	A044	BJ	W1060	860	22		21-66-21	050-099, 162-199
	Y	A045	BJ	W1060	863	22		21-66-31	050-099, 150, 152-199
	Y	A045	BJ	W1102	120	22		21-66-31	050-099, 150, 152-199
	F	A047	2	W1104	121	16		33-21-31	166
	F	A047	2	W1104	829	16		33-21-31	166
	X	A048	BJ	W1104	800	20		33-21-31	155-156, 166
	X	A048	BJ	W1104	824	20		33-21-31	155-156, 166

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 236

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	F	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	G	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	H	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	X	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	Y	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	Z	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	X	A049	BJ	W1104	806	20		33-21-31	155-156, 166
	X	A049	BJ	W1104	828	20		33-21-31	155-156, 166
	X	B007	BJ	W1058	038	22		33-26-21	280-299
	X	B007	BJ	W1104	602	20		33-26-21	275-299
	X	B008	BJ	W1060	505	22		33-27-11	ALL
	X	B008	BJ	W1104	131	22		33-27-11	ALL
	X	B042	BJ	W1104	726	20		33-21-31	155-156, 166
	X	B042	BJ	W1104	823	20		33-21-31	155-156, 166
	X	B048	BJ	W1104	803	20		33-21-31	155-156, 166
	X	B048	BJ	W1104	825	20		33-21-31	155-156, 166
	Y	C001	BJ	W1060	717	20		33-26-11	050-099, 150-199
	Y	C001	BJ	W1104	651	20		33-26-11	050-099
	Y	C001	BJ	W1104	652	20		33-26-11	050-099, 150-199
	Y	C002	BJ	W1060	762	24		33-21-11	050-099, 150-199
	Y	C002	BJ	W1060	790	24		33-21-31	050-099, 150-199
	Y	C002	BJ	W1104	650	24		33-21-11	050-099, 150-199
	F	C003	2	W1058	018	24		21-24-11	050-099, 150-199
	F	C003	2	W1102	021	24		21-24-11	050-099, 150-199
	Y	C005	BJ	W1058	004	22		33-25-11	275-299
	Y	C005	BJ	W1058	038	20		33-26-21	050-099
	Y	C005	BJ	W1060	620	20		33-26-21	050-099
	Y	C005	BJ	W1060	823	20		33-26-21	050-099
	Y	C005	BJ	W1104	591	22		33-25-11	275-299
	Y	C006	BJ	W1060	105	22		33-26-11	ALL
	Y	C006	BJ	W1104	114	22		33-26-11	275-299
	Y	C006	BJ	W1104	149	22		33-26-11	ALL
	Y	C006	BJ	W1104	593	22		33-26-11	050-099, 275-299
	X	C007	BJ	W1060	504	22		33-27-11	ALL
	X	C007	BJ	W1104	129	22		33-27-11	ALL
	X	C008	BJ	W1058	019	22		38-32-12	050-099
	X	C008	BJ	W1058	019	20		38-32-12	150-156, 162-165, 275-276
	X	C008	BJ	W1058	019	20		38-32-16	157, 166-199, 277-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 237

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	X	C008	BJ	W1102	024	22		38-32-12	050-099
	X	C008	BJ	W1102	024	20		38-32-12	150-156, 162-165, 275-276
	X	C008	BJ	W1102	024	20		38-32-16	157, 166-199, 277-299
	X	C010	BJ	W1058	604	22		33-25-11	050-099, 150-199
	X	C010	BJ	W1102	608	22		33-25-11	050-099, 150-199
	Y	C012	BJ	W1060	01U	22		33-21-21	280-299
	Y	C012	BJ	W1060	624	22		33-21-21	150-157, 280-299
	Y	C012	BJ	W1060	680	22		33-21-21	150-157, 280-299
	Y	C012	BJ	W1060	682	22		33-21-21	150-157, 280-299
	Y	C012	BJ	W1060	686	22		33-21-21	150-157
	Y	C014	BJ	W1060	01X	20		33-24-11	280-299
	Y	C014	BJ	W1060	715	20		33-24-11	280-299
	Y	C014	BJ	W1060	792	20		33-24-11	280-299
	Y	C015	BJ	W1060	066	24		33-24-11	ALL
	Y	C015	BJ	W1060	073	24		33-24-11	ALL
	Y	C015	BJ	W1060	079	24		33-24-11	ALL
	Y	C016	BJ	W1058	001	22		33-24-11	ALL
	Y	C016	BJ	W1060	091	22		33-24-11	ALL
	Y	C016	BJ	W1102	007	22		33-24-11	ALL
	Y	C016	BJ	W1104	102	22		33-24-11	ALL
	Y	C017	BJ	W1058	075	22		33-25-11	050-099
	Y	C017	BJ	W1060	098	22		33-25-11	050-099
	Y	C017	BJ	W1102	086	22		33-25-11	050-099
	F	C024	2	W1060	767	22		33-22-41	050-099, 150-199
	F	C024	2	W1104	643	22		33-22-41	050-099, 150-199
	Y	C027	BJ	W1104	006	20		33-21-11	150-199
	Y	C027	BJ	W1104	025	20		33-21-11	150-199
	Y	C027	BJ	W1104	026	20		33-21-11	150-199
	Y	C028	BJ	W1104	165	20		33-21-11	275-277, 280-299
	Y	C028	BJ	W1104	165	20		SPARE	278
	Y	C028	BJ	W1104	532	20		33-21-11	150-199, 275-299
	Y	C028	BJ	W1104	596	20		33-21-11	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 238

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Y	C028	BJ	W1104	598	20		33-21-11	275-299
	Y	C028	BJ	W1104	728	20		33-21-11	150-199
	Y	C031	BJ	W1060	745	24		33-21-31	050-099, 150-199
	Y	C031	BJ	W1104	010	24		33-21-11	050-099
	Y	C031	BJ	W1104	010	20		33-21-11	150-199
	Y	C031	BJ	W1104	035	24		33-21-11	050-099, 150-199
	Y	C037	BJ	W1104	036	20		33-21-11	150-199
	Y	C037	BJ	W1104	045	20		33-21-11	150-199
	Y	C037	BJ	W1104	046	20		33-21-11	150-199
	X	C041	BJ	W1058	064	20		26-13-12	162-199
	X	C041	BJ	W1060	800	20		26-13-12	162-199
	X	C042	BJ	W1104	722	20		33-21-31	155-156
	X	C042	BJ	W1104	777	20		33-21-31	155-156
	Y	C043	BJ	W1060	740	20		33-21-31	151-152, 155-157
	Y	C043	BJ	W1060	851	24		33-21-31	162-199
	Y	C043	BJ	W1104	724	24		33-21-31	150-199
	Y	C043	BJ	W1104	800	24		33-21-31	150-154, 157-165, 167-199
	Y	C043	BJ	W1104	831	24		33-21-31	166
	Y	C044	BJ	W1060	862	22		21-66-31	050-099, 150, 152-199
	Y	C044	BJ	W1102	118	22		21-66-31	050-099, 150, 152-199
	Y	C044	BJ	W1102	119	22		21-66-31	050-099, 150, 152-199
	Y	C045	BJ	W1058	084	22		21-66-11	050-099, 162-199
	Y	C045	BJ	W1060	873	22		21-66-11	050-099, 162-199
	Y	C045	BJ	W1060	881	22		21-66-11	050-099, 162-199
	X	C048	BJ	W1104	804	20		33-21-31	155-156, 166
	X	C048	BJ	W1104	826	20		33-21-31	155-156, 166
	X	D008	BJ	W1058	605	22		33-26-21	275-278
	X	D008	BJ	W1058	618	22		33-26-21	275-278
	X	D008	BJ	W1102	042	20		33-26-21	280-299
	X	D008	BJ	W1104	121	20		33-26-21	280-299
	X	D041	BJ	W1058	081	20		26-13-12	162-199
	X	D041	BJ	W1060	847	20		26-13-12	162-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 239

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0146		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0146		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0146	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0146	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	X	D042	BJ	W1104	074	20		33-21-31	166
	X	D042	BJ	W1104	822	20		33-21-31	166
	X	D048	BJ	W1104	805	20		33-21-31	155-156, 166
	X	D048	BJ	W1104	827	20		33-21-31	155-156, 166
	Z	DED		W1058	022Z			33-24-11	277-299
	Z	DED		W1104	127Z			33-27-11	155-156, 166
	Z	DED		W1104	130Z			33-27-11	155-156, 166
	X	DED		W1104	777Z			33-21-31	155-156
	X	DED		W1104	822Z			33-21-31	166
	X	DED		W1104	823Z			33-21-31	155-156, 166
	X	DED		W1104	824Z			33-21-31	155-156, 166
	X	DED		W1104	825Z			33-21-31	155-156, 166
	X	DED		W1104	826Z			33-21-31	155-156, 166
	X	DED		W1104	827Z			33-21-31	155-156, 166
	X	DED		W1104	828Z			33-21-31	155-156, 166
	F	DED		W1104	829Z			33-21-31	166
	Z	DED		W1110	078Z			33-24-11	277-278
	Z	DED		W1110	091Z			33-51-11	ALL
<b>TB0148</b>		<b>BACT44B1350U</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0148</b>	<b>D</b>	<b>YHLZD-30</b>					<b>P025-00/ /</b>		<b>050-099, 150-199</b>
<b>TB0148</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0148</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0148</b>	<b>H</b>	<b>BACM15C2A</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0148</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0148</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0148</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P025-00/ /</b>		<b>ALL</b>
	Z	13	BJ	W1064	007	22		33-21-21	150-199, 275-299
	Z	13	BJ	W1064	009	22		33-21-21	ALL
	Z	13	BJ	W1064	012	22		33-21-21	150-199, 275-299
	Z	13	BJ	W1064	013	22		33-21-21	ALL
	Z	13	BJ	W1064	124	22		33-21-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 240

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0148		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	D	<b>YHLZD-30 (continued)</b>					<b>P025-00/ /</b>		<b>050-099, 150-199</b>
TB0148	F	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	G	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	H	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	X	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	Y	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	Z	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	Z	13	BJ	W1064	502	22		33-21-21	ALL
	Z	14	BJ	W1064	033	20		33-26-21	ALL
	Z	14	BJ	W1106	115	20		33-26-21	150-199, 275-299
	Z	14	BJ	W1106	116	20		33-26-11	150-199
	Z	14	BJ	W1106	133	20		33-26-21	280-299
	Z	14	BJ	W1106	159	20		33-26-21	050-099
	Z	14	BJ	W1106	161	22		33-26-11	150-199
	Z	14	BJ	W1108	044	20		33-26-21	ALL
	Z	14	BJ	W1108	068	20		33-26-11	ALL
	Z	14	BJ	W1108	514	20		33-26-21	050-099
	Z	14	BJ	W1108	517	20		33-26-21	050-099
	Z	14	BJ	W1108	519	20		33-26-21	050-099, 162-199
	Z	14	BJ	W1108	617	22		33-26-11	150-199
	Z	17	BJ	W1064	093	22		33-22-42	150, 152-199
	Z	17	BJ	W1064	900	22		33-22-42	150, 152-199
	Z	17	BJ	W1108	646	22		33-22-42	150, 152-199
	Z	18	BJ	W1064	004	22		33-21-21	ALL
	Z	18	BJ	W1064	008	22		33-21-21	ALL
	Z	18	BJ	W1064	097	22		33-21-21	162-199
	Z	18	BJ	W1064	501	22		33-21-21	ALL
	Z	18	BJ	W1064	637	22		33-21-21	050-099
	Z	18	BJ	W1064	638	22		33-21-21	050-099
	Z	18	BJ	W1064	642	22		33-21-21	162-199
	Z	27	BJ	W1064	610	22		33-22-42	050-099, 150-199
	Z	27	BJ	W1064	611	22		33-22-42	050-099, 150-199
	Z	27	BJ	W1064	626	24		33-21-12	050-099, 150-199
	Z	27	BJ	W1108	622	24		33-21-12	050-099, 150-199
	Z	27	BJ	W1108	623	24		33-21-12	050-099, 150-199
	Z	27	BJ	W1108	624	24		33-21-12	050-099, 150-199
	Z	27	BJ	W1108	626	24		33-21-12	050-099, 150-199
	G	40	2	W1064	617	18		33-27-11	150-199
	G	40	2	W1108	647	18		33-27-11	150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 241

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0148		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P025-00/ /</b>		<b>050-099, 150-199</b>
TB0148	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	X	A005	BJ	W1064	621	22		33-22-42	050-099, 150-199
	X	A005	BJ	W1108	632	22		33-22-42	050-099, 150-199
	X	A006	BJ	W1064	606	22		33-21-21	050-099, 150-199
	X	A006	BJ	W1108	184	22		33-21-21	050-099, 150-199
	X	A007	BJ	W1106	132	20		33-26-21	275-299
	X	A007	BJ	W1108	115	20		33-26-21	275-299
	X	A008	BJ	W1064	152	24		33-21-12	050-099, 150-199
	X	A008	BJ	W1108	086	24		33-21-12	150-199
	X	A008	BJ	W1108	195	24		33-21-12	050-099
	Y	A009	BJ	W1106	115	20		33-26-21	150-199
	Y	A009	BJ	W1106	159	20		33-26-21	150-199
	Y	A009	BJ	W1106	160	20		33-26-21	150-199
	Y	A009	BJ	W1106	500	20		33-26-21	050-099
	Y	A009	BJ	W1106	501	20		33-26-21	050-099
	Y	A009	BJ	W1108	512	20		33-26-21	050-099
	Y	A009	BJ	W1108	620	20		33-26-21	150-199
	Y	A010	BJ	W1106	191	20		26-13-11	050-099
	Y	A010	BJ	W1108	523	20		26-13-11	050-099
	Y	A010	BJ	W1108	611	20		26-13-11	050-099
	Y	A011	BJ	W1106	602	22		33-25-11	050-099
	Y	A011	BJ	W1108	012	20		33-21-12	150-199, 275-299
	Y	A011	BJ	W1108	032	20		33-21-12	150-199, 275-299
	Y	A011	BJ	W1108	033	20		33-21-12	150-199, 275-299
	Y	A011	BJ	W1108	670	22		33-25-11	050-099
	Y	A011	BJ	W1108	671	22		33-25-11	050-099
	Y	A012	BJ	W1064	625	22		33-22-42	050-099, 150-199
	Y	A012	BJ	W1108	003	24		33-21-12	050-099, 150-199
	Y	A012	BJ	W1108	004	20		33-21-12	280-299
	Y	A012	BJ	W1108	071	24		33-21-12	050-099, 150-199
	Y	A012	BJ	W1108	602	20		33-21-12	280-299
	Y	A012	BJ	W1108	630	20		33-21-12	280-299
	D	A023	2	W1106	150	22		33-25-11	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 242

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0148		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P025-00/ /</b>		<b>050-099, 150-199</b>
TB0148	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	D	A024	2	W1106	152	22		33-25-11	050-099, 150-154, 156, 162-199
	D	A024	2	W1106	198	22		33-25-11	155, 157
	D	A024	2	W1108	039	22		33-25-11	050-099
	D	A026	2	W1108	621	22		33-25-11	050-099, 150-199
	D	A029	2	W1106	601	22		33-25-11	150-199
	D	A029	2	W1108	666	22		33-25-11	050-099
	D	A029	2	W1108	669	22		33-25-11	050-099
	D	A030	2	W1106	142	22		33-25-11	050-099
	D	A030	2	W1106	198	22		33-25-11	155, 157
	D	A030	2	W1106	603	22		33-25-11	150-199
	D	A030	2	W1108	673	22		33-25-11	050-099
	Y	A033	BJ	W1108	129	22		38-32-13	150-156, 162-165, 275-276
	Y	A033	BJ	W1108	129	22		38-32-16	157, 166-199, 277-299
	Y	A033	BJ	W1108	131	22		38-32-13	275-276
	Y	A033	BJ	W1108	131	22		38-32-16	277-299
	Y	A033	BJ	W1108	135	22		38-32-13	150-156, 162-165, 275-276
	Y	A033	BJ	W1108	135	22		38-32-16	157, 166-199, 277-299
	Y	A034	BJ	W1064	120	22		21-66-31	150, 152-199
	Y	A034	BJ	W1064	569	22		21-66-31	050-099
	Y	A034	BJ	W1108	085	22		21-66-31	050-099, 150, 152-199
	Y	A037	BJ	W1106	192	20		26-13-11	050-099
	Y	A037	BJ	W1108	520	20		26-13-11	050-099
	Y	A037	BJ	W1108	612	20		26-13-11	050-099
	X	B005	BJ	W1064	623	22		33-22-42	050-099, 150-199
	X	B005	BJ	W1108	633	22		33-22-42	050-099, 150-199
	X	B006	BJ	W1064	608	24		33-21-21	050-099, 150-199
	X	B006	BJ	W1108	185	24		33-21-21	050-099, 150-199
	X	C005	BJ	W1106	154	22		33-25-11	155, 157
	X	C005	BJ	W1108	173	22		33-25-11	155, 157
	X	C006	BJ	W1064	609	24		33-21-21	050-099, 150-199
	X	C006	BJ	W1108	187	24		33-21-21	050-099, 150-199
	X	C007	BJ	W1106	160	20		33-26-21	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 243

Aug 05/2009





Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0148		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P025-00/ /</b>		<b>050-099, 150-199</b>
TB0148	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	X	C007	BJ	W1108	518	20		33-26-21	050-099
	X	C008	BJ	W1064	629	24		33-21-12	050-099, 150-199
	X	C008	BJ	W1108	193	24		33-21-12	050-099, 150-199
	Y	C009	BJ	W1106	190	20		26-13-11	050-099
	Y	C009	BJ	W1108	522	20		26-13-11	050-099
	Y	C009	BJ	W1108	610	20		26-13-11	050-099
	Y	C010	BJ	W1106	107	22		33-25-11	ALL
	Y	C010	BJ	W1106	142	22		33-25-11	150-199, 275-299
	Y	C010	BJ	W1108	039	22		33-25-11	150-199, 275-299
	Y	C010	BJ	W1108	116	22		33-25-11	050-099, 150-199
	Y	C010	BJ	W1108	672	22		33-25-11	050-099
	Y	C011	BJ	W1108	026	20		33-21-12	150-199, 275-299
	Y	C011	BJ	W1108	027	20		33-21-12	150-199, 275-299
	Y	C011	BJ	W1108	075	20		33-21-12	150-199, 275-299
	Y	C012	BJ	W1108	029	20		33-21-12	280-299
	Y	C012	BJ	W1108	073	20		33-21-12	280-299
	Y	C012	BJ	W1108	631	20		33-21-12	280-299
	D	C023	2	W1106	151	22		33-25-11	050-099, 150-199
	D	C023	2	W1106	605	22		33-25-11	050-099, 150-199
	D	C024	2	W1106	152	22		33-25-11	155, 157
	D	C024	2	W1106	154	22		33-25-11	050-099, 150-154, 156, 162-199
	D	C026	2	W1106	151	22		33-25-11	050-099, 150-199
	D	C029	2	W1106	602	22		33-25-11	150-199
	D	C029	2	W1108	667	22		33-25-11	050-099
	D	C029	2	W1108	668	22		33-25-11	050-099
	D	C030	2	W1106	604	22		33-25-11	150-199
	D	C030	2	W1108	668	22		33-25-11	050-099
	Y	C033	BJ	W1108	066	20		38-32-13	150-156, 162-165, 275-276
	Y	C033	BJ	W1108	066	20		38-32-16	157, 166-199, 277-299
	Y	C033	BJ	W1108	119	20		38-32-13	150-156, 162-165, 275-276
	Y	C033	BJ	W1108	119	20		38-32-16	157, 166-199, 277-299
	Y	C033	BJ	W1108	121	20		38-32-13	275-276

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 244

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0148		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P025-00/ /</b>		<b>050-099, 150-199</b>
TB0148	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0148	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	Y	C033	BJ	W1108	121	20		38-32-16	277-299
	X	D006	BJ	W1106	189	20		26-13-11	050-099
	X	D006	BJ	W1108	521	20		26-13-11	050-099
	X	D007	BJ	W1106	600	20		38-32-12	050-099, 150-156, 162-165
	X	D007	BJ	W1106	600	20		38-32-16	157, 166-199
	X	D007	BJ	W1108	601	20		38-32-12	050-099, 150-156, 162-165
	X	D007	BJ	W1108	601	20		38-32-16	157, 166-199
	X	D008	BJ	W1064	630	24		33-21-12	150-199
	X	D008	BJ	W1108	189	24		33-21-12	150-199
<b>TB0158</b>		<b>BACT44B0940U</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0158</b>	<b>D</b>	<b>DIODEBLOCK-REF284T0049-</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0158</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0158</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0158</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0158</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0158</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P050-00/ /</b>		<b>ALL</b>
	G	1	2	W1078	184	24		34-61-13	150-199, 275-276
	G	1	2	W1080	502	24		34-61-13	150-199, 275-276
	G	1	2	W1080	507	24		34-61-23	150-199, 275-276
	G	10	2	W1078	029	24		73-21-15	ALL
	G	10	2	W1080	720	24		73-21-15	ALL
	G	10	2	W1114	091	24		73-21-15	ALL
	G	16	2	W1078	708	24		21-51-21	ALL
	G	16	2	W1080	028	22		21-51-21	ALL
	G	16	2	W1080	034	22		21-51-21	ALL
	G	18	2	W1078	185	24		34-61-13	ALL
	G	18	2	W1080	503	24		34-61-13	ALL
	G	18	2	W1080	508	24		34-61-23	ALL
	G	2	2	W1080	092	24		21-58-11	150-199, 275-276
	G	2	2	W1080	768	24		21-58-11	150-199, 275-276
	G	2	2	W1114	117	24		21-58-11	150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 245

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0158		BACT44B0940U (continued)					P050-00/ /		ALL
TB0158	D	DIODEBLOCK-REF284T0049- (continued)					P050-00/ /		ALL
TB0158	F	BACM15C1A (continued)					P050-00/ /		ALL
TB0158	G	BACM15C1B (continued)					P050-00/ /		ALL
TB0158	X	BACM15C3A (continued)					P050-00/ /		ALL
TB0158	Y	BACM15C3B (continued)					P050-00/ /		ALL
TB0158	Z	BACM15C3C (continued)					P050-00/ /		ALL
	G	21	2	W1078	186	24		34-61-13	ALL
	G	21	2	W1080	504	24		34-61-13	ALL
	G	21	2	W1080	509	24		34-61-23	ALL
	G	22	2	W1078	187	24		34-61-13	ALL
	G	22	2	W1080	505	24		34-61-13	ALL
	G	22	2	W1080	510	24		34-61-23	ALL
	G	23	2	W1078	188	24		34-61-13	ALL
	G	23	2	W1080	506	24		34-61-13	ALL
	G	23	2	W1080	511	24		34-61-23	ALL
	G	27	2	W1078	055	24		21-58-14	050-099
	G	27	2	W1078	527	24		21-58-14	050-099
	Z	27	BJ	W1080	211Z			77-12-12	150-157, 275-276
	Z	27	BJ	W1080	218Z			77-12-12	150-157, 275-276
	G	27	2	W1114	112	24		21-58-14	050-099
	Z	27	BJ	W1114	213F	20		77-12-12	150-157, 275-276
	Z	27	BJ	W1114	213Z			77-12-12	150-157, 275-276
	Z	27	BJ	W1114	214Z			77-12-12	150-157, 275-276
	Z	28	BJ	W1078	211Z			77-12-12	150-157, 275-276
	Z	28	BJ	W1078	250Z			77-12-12	150-157, 275-276
	Z	28	BJ	W1114	211F	20		77-12-12	150-157, 275-276
	Z	28	BJ	W1114	211Z			77-12-12	150-157, 275-276
	Z	28	BJ	W1114	212Z			77-12-12	150-157, 275-276
	G	3	2	W1078	007	24		21-51-11	150-199, 275-276
	G	3	2	W1078	031	24		21-51-11	150-199, 275-276
	G	3	2	W1080	008	24		21-51-11	150-199, 275-276
	G	4	2	W1078	008	24		21-51-21	150-199, 275-276
	G	4	2	W1080	007	24		21-51-21	150-199, 275-276
	G	4	2	W1080	143	24		21-51-21	150-199, 275-276
	G	9	2	W1078	034	24		21-51-21	050-099, 150-199
	G	9	2	W1078	034	24		21-51-11	275-299
	G	9	2	W1078	036	24		21-51-21	050-099, 166-199, 275-299
	G	9	2	W1078	036	22		21-51-21	150-165
	G	9	2	W1080	525	24		21-51-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 246

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0158		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
	Y	A002	BJ	W1078	055	24		21-58-14	277-299
	Y	A002	BJ	W1078	527	24		21-58-14	277-299
	Y	A002	BJ	W1114	112	24		21-58-14	277-299
	Y	A003	BJ	W1078	184	24		34-61-13	050-099, 277-299
	Y	A003	BJ	W1080	502	24		34-61-13	050-099, 277-299
	Y	A003	BJ	W1080	507	24		34-61-23	050-099, 277-299
	Y	A004	BJ	W1078	007	24		21-51-11	050-099, 277-299
	Y	A004	BJ	W1078	031	24		21-51-11	050-099, 277-299
	Y	A004	BJ	W1080	008	24		21-51-11	050-099, 277-299
	Y	A005	BJ	W1078	015	24		21-51-11	ALL
	Y	A005	BJ	W1078	090	24		21-51-11	150-199, 275-299
	Y	A005	BJ	W1114	003	24		21-51-11	ALL
	Y	A006	BJ	W1078	505	24		73-21-15	050-099, 153-199, 277-299
	Y	A006	BJ	W1078	506	24		34-61-13	050-099, 153-199, 277-299
	Y	A006	BJ	W1080	530	24		73-21-15	050-099, 153-199, 277-299
	Y	A007	BJ	W1080	123	24		36-11-52	ALL
	Y	A007	BJ	W1080	139	24		36-11-52	ALL
	Y	A007	BJ	W1080	140	24		36-11-52	ALL
	Y	A008	BJ	W1080	013	24		21-51-21	150-199, 275-299
	Y	A008	BJ	W1080	014	24		21-51-21	ALL
	Y	A008	BJ	W1114	006	24		21-51-21	ALL
	F	A011	2	W1080	109	22		21-58-11	ALL
	F	A011	2	W1114	111	22		21-58-11	ALL
	F	A012	2	W1078	023	24		21-51-11	ALL
	F	A012	2	W1080	075	24		21-53-12	ALL
	D	A013	2	W1080	522	22		27-61-11	153-154
	D	A013	2	W1080	559	22		27-61-11	050-099, 155-156, 162-166
	Y	A014	BJ	W1078	505	24		73-21-15	150-152, 275-276
	Y	A014	BJ	W1078	506	24		34-61-13	150-152, 275-276
	D	A014	2	W1078	522	22		34-45-13	153-154
	D	A014	2	W1078	558	22		34-45-13	050-099, 155-156, 162-166
	Y	A014	BJ	W1080	530	24		73-21-15	150-152, 275-276
	F	A017	2	W1078	052	24		21-26-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 247

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0158		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
	F	A017	2	W1080	01A	24		21-26-11	156-157, 166-199, 277-299
	F	A017	2	W1080	029	24		21-26-11	050-099, 150-155, 162-165, 275-276
	F	A019	2	W1078	207B	24		27-51-31	ALL
	F	A019	2	W1114	201B	24		27-51-31	ALL
	F	A020	2	W1078	116	24		21-26-11	ALL
	F	A020	2	W1080	776	24		21-26-11	ALL
	F	A024	2	W1078	766	24		27-51-31	ALL
	F	A024	2	W1114	121	24		27-51-31	ALL
	Y	A025	BJ	W1080	211R	24		77-12-12	150-157, 275-276
	Y	A025	BJ	W1080	218R	24		77-12-12	150-157, 275-276
	Y	A025	BJ	W1114	213R	24		77-12-12	150-157, 275-276
	Y	A025	BJ	W1114	214R	24		77-12-12	150-157, 275-276
	Y	A026	BJ	W1078	211R	24		77-12-12	150-157, 275-276
	Y	A026	BJ	W1078	250R	24		77-12-12	150-157, 275-276
	Y	A026	BJ	W1114	211R	24		77-12-12	150-157, 275-276
	Y	A026	BJ	W1114	212R	24		77-12-12	150-157, 275-276
	Y	C003	BJ	W1080	092	24		21-58-11	050-099, 277-299
	Y	C003	BJ	W1080	768	24		21-58-11	050-099, 277-299
	Y	C003	BJ	W1114	117	24		21-58-11	050-099, 277-299
	Y	C004	BJ	W1078	008	24		21-51-21	050-099, 277-299
	Y	C004	BJ	W1080	007	24		21-51-21	050-099, 277-299
	Y	C004	BJ	W1080	143	24		21-51-21	050-099, 277-299
	Y	C005	BJ	W1078	094	24		36-11-51	ALL
	Y	C005	BJ	W1078	106	24		36-11-51	ALL
	Y	C005	BJ	W1078	107	24		36-11-51	ALL
	Y	C006	BJ	W1078	014	24		21-51-11	ALL
	Y	C006	BJ	W1078	035	24		21-51-11	150-199, 275-299
	Y	C006	BJ	W1114	004	24		21-51-11	ALL
	Y	C007	BJ	W1080	015	24		21-51-21	ALL
	Y	C007	BJ	W1080	024	24		21-51-21	150-199, 275-299
	Y	C007	BJ	W1114	005	24		21-51-21	ALL
	Y	C008	BJ	W1078	055	24		21-58-14	153-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 248

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0158		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
	Y	C008	BJ	W1078	527	24		21-58-14	153-199
	Y	C008	BJ	W1080	001	24		21-51-21	275-299
	Y	C008	BJ	W1080	010	24		31-51-41	050-099
	Y	C008	BJ	W1080	012	24		21-51-21	275-299
	Y	C008	BJ	W1114	043	24		31-51-41	050-099
	Y	C008	BJ	W1114	112	24		21-58-14	153-199
	F	C011	2	W1080	089	24		21-58-11	ALL
	F	C011	2	W1114	114	24		21-58-11	ALL
	F	C012	2	W1078	071	24		21-53-22	ALL
	F	C012	2	W1080	023	24		21-53-22	ALL
	D	C013	2	W1080	521	22		27-61-11	050-099, 153-156, 162-166
	D	C013	2	W1080	529	22		27-61-11	153-154
	D	C013	2	W1080	560	22		27-61-11	050-099, 155-156, 162-166
	Y	C014	BJ	W1078	055	24		21-58-14	150-152, 275-276
	Y	C014	BJ	W1078	527	24		21-58-14	150-152, 275-276
	D	C014	2	W1080	529	22		27-61-11	153-154
	D	C014	2	W1080	560	22		27-61-11	050-099, 155-156, 162-166
	Y	C014	BJ	W1114	112	24		21-58-14	150-152, 275-276
	F	C017	2	W1078	059	24		21-58-14	ALL
	F	C017	2	W1080	067	24		21-58-15	ALL
	F	C019	2	W1078	207R	24		27-51-31	ALL
	F	C019	2	W1114	201R	24		27-51-31	ALL
	F	C020	2	W1078	063	24		21-58-14	ALL
	F	C020	2	W1080	063	24		21-58-15	ALL
	F	C024	2	W1078	019	24		21-51-11	ALL
	F	C024	2	W1114	033	24		21-51-11	ALL
	Y	C025	BJ	W1080	211B	24		77-12-12	150-157, 275-276
	Y	C025	BJ	W1080	218B	24		77-12-12	150-157, 275-276
	Y	C025	BJ	W1114	213B	24		77-12-12	150-157, 275-276
	Y	C025	BJ	W1114	214B	24		77-12-12	150-157, 275-276
	Y	C026	BJ	W1078	211B	24		77-12-12	150-157, 275-276
	Y	C026	BJ	W1078	250B	24		77-12-12	150-157, 275-276
	Y	C026	BJ	W1114	211B	24		77-12-12	150-157, 275-276

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 249

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0158		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0158	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
	Y	C026	BJ	W1114	212B	24		77-12-12	150-157, 275-276
	G	DED		W1078	184Z			34-61-13	050-099, 150-199, 275-276
	Y	DED		W1078	184Z			34-61-13	277-299
	G	DED		W1078	185Z			34-61-13	ALL
	G	DED		W1078	186Z			34-61-13	ALL
	G	DED		W1078	187Z			34-61-13	ALL
	G	DED		W1078	188Z			34-61-13	ALL
	F	DED		W1080	089Z			21-58-11	ALL
	Y	DED		W1114	043Z			31-51-41	050-099
<b>TB0160</b>		<b>BACT44B1350U</b>					<b>P019-00/ /</b>		<b>050-099</b>
<b>TB0160</b>		<b>BACT44B1550U</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
<b>TB0160</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P019-00/ /</b>		<b>ALL</b>
<b>TB0160</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P019-00/ /</b>		<b>ALL</b>
<b>TB0160</b>	<b>H</b>	<b>BACM15C2A</b>					<b>P019-00/ /</b>		<b>ALL</b>
<b>TB0160</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P019-00/ /</b>		<b>ALL</b>
<b>TB0160</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P019-00/ /</b>		<b>ALL</b>
<b>TB0160</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P019-00/ /</b>		<b>ALL</b>
	H	1	2	W1060	104	20		33-51-11	ALL
	H	1	2	W1060	112	20		33-51-11	ALL
	H	1	2	W1060	113	20		33-51-11	ALL
	H	1	2	W1060	524	22		33-51-11	ALL
	H	1	2	W1060	601	22		25-65-12	ALL
	H	1	2	W1060	602	22		25-65-12	ALL
	H	1	2	W1060	604	22		25-65-12	ALL
	H	1	2	W1060	642	20		33-51-11	ALL
	Z	10	BJ	W1060	106	22		33-51-11	ALL
	Z	10	BJ	W1060	119	22		33-51-11	ALL
	Z	10	BJ	W1060	133	22		33-51-11	ALL
	Z	10	BJ	W1060	137	22		33-51-11	ALL
	Z	10	BJ	W1060	568	22		33-51-11	ALL
	Z	10	BJ	W1060	641	22		33-51-11	ALL
	Z	11	BJ	W1060	117	22		33-51-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 250

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0160		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0160		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0160	F	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	G	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	H	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	X	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	Y	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	Z	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Z	11	BJ	W1060	121	22		33-51-11	ALL
	Z	11	BJ	W1060	128	22		33-51-11	ALL
	Z	11	BJ	W1060	157	22		33-51-21	ALL
	Z	11	BJ	W1060	525	22		33-51-11	ALL
	Z	11	BJ	W1060	567	22		33-51-11	ALL
	Z	11	BJ	W1060	572	22		33-51-21	ALL
	Z	11	BJ	W1060	573	22		33-51-21	ALL
	G	18	2	W1058	036	24		35-21-11	ALL
	G	18	2	W1110	003	22		35-21-11	ALL
	G	18	2	W1110	023	22		35-21-11	ALL
	G	18	2	W1110	031	22		35-21-11	ALL
	H	19	2	W1110	002	24		35-21-11	ALL
	H	19	2	W1110	009	24		35-21-11	ALL
	H	19	2	W1110	010	24		35-21-11	ALL
	H	19	2	W1110	021	24		35-21-11	ALL
	H	19	2	W1110	024	24		35-21-11	ALL
	G	22	2	W1110	015	24		35-21-11	ALL
	G	22	2	W1110	016	24		35-21-11	ALL
	G	22	2	W1110	017	24		35-21-11	ALL
	G	24	2	W1110	008	24		35-21-11	ALL
	G	24	2	W1110	025	24		35-21-11	ALL
	G	24	2	W1110	026	24		35-21-11	ALL
	G	26	2	W1110	007	24		35-21-11	ALL
	G	26	2	W1110	033	24		35-21-11	ALL
	G	26	2	W1110	034	24		35-21-11	ALL
	G	28	2	W1110	037	16		35-21-12	ALL
	G	28	2	W1110	038	16		35-21-12	ALL
	G	28	2	W1110	041	16		35-21-12	ALL
	H	29	2	W1104	780	20		35-21-12	280-299
	H	29	2	W1110	039	16		35-21-12	ALL
	H	29	2	W1110	040	16		35-21-12	ALL
	H	29	2	W1110	042	16		35-21-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 251

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0160		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0160		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0160	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	H	29	2	W1110	043	16		35-21-12	ALL
	H	29	2	W1110	044	20		35-21-12	ALL
	H	3	2	W1060	146	20		33-51-21	ALL
	H	3	2	W1060	147	20		33-51-21	ALL
	H	3	2	W1060	596	22		25-65-11	ALL
	H	3	2	W1060	640	20		33-51-11	ALL
	H	3	2	W1110	088	20		33-51-11	ALL
	G	31	2	W1110	045	16		35-21-13	ALL
	G	31	2	W1110	046	16		35-21-13	ALL
	G	31	2	W1110	048	16		35-21-13	ALL
	H	32	2	W1110	047	16		35-21-13	ALL
	H	32	2	W1110	049	16		35-21-13	ALL
	H	32	2	W1110	050	20		35-21-13	050-099, 150-199
	H	32	2	W1110	051	16		35-21-13	ALL
	H	32	2	W1110	052	16		35-21-13	ALL
	G	34	2	W1110	053	16		35-21-14	ALL
	G	34	2	W1110	054	16		35-21-14	ALL
	G	34	2	W1110	056	16		35-21-14	ALL
	H	35	2	W1060	820	20		35-21-14	050-099, 162-199
	H	35	2	W1110	055	16		35-21-14	ALL
	H	35	2	W1110	057	16		35-21-14	ALL
	H	35	2	W1110	058	20		35-21-14	275-299
	H	35	2	W1110	059	16		35-21-14	ALL
	H	35	2	W1110	060	16		35-21-14	ALL
	G	37	2	W1060	025	20		33-51-11	ALL
	G	37	2	W1060	115	20		33-51-11	ALL
	G	37	2	W1060	116	20		33-51-11	ALL
	G	37	2	W1060	640	20		33-51-11	ALL
	H	39	2	W1110	001	24		35-21-11	ALL
	H	39	2	W1110	004	24		35-21-11	ALL
	H	39	2	W1110	005	24		35-21-11	ALL
	H	39	2	W1110	011	24		35-21-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 252

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0160		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0160		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0160	F	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	G	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	H	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	X	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	Y	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	Z	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	H	39	2	W1110	032	24		35-21-11	ALL
	G	7	2	W1110	018	24		35-21-11	ALL
	G	7	2	W1110	019	24		35-21-11	ALL
	G	7	2	W1110	022	24		35-21-11	ALL
	Y	A012	BJ	W1060	139	22		33-51-21	ALL
	Y	A012	BJ	W1060	152	22		33-51-21	ALL
	Y	A012	BJ	W1104	107	22		33-51-21	ALL
	Y	A013	BJ	W1060	148	20		33-51-21	ALL
	Y	A013	BJ	W1060	154	20		33-51-21	ALL
	Y	A013	BJ	W1060	158	20		33-51-21	ALL
	Y	A014	BJ	W1060	060	22		33-51-11	ALL
	Y	A014	BJ	W1104	027	22		33-51-11	ALL
	Y	A014	BJ	W1104	193	22		33-51-11	ALL
	Y	A015	BJ	W1058	035	22		33-51-11	ALL
	Y	A015	BJ	W1060	110	22		33-51-11	050-099, 150-199
	Y	A015	BJ	W1060	569	22		33-51-11	ALL
	Y	A016	BJ	W1060	043	22		33-22-41	ALL
	Y	A016	BJ	W1060	044	22		33-22-41	275-299
	Y	A016	BJ	W1060	045	22		33-22-41	ALL
	Y	A016	BJ	W1104	736	22		33-22-41	050-099, 150-199
	F	A021	2	W1058	211B	20		21-65-11	ALL
	F	A021	2	W1060	249B	20		21-65-11	ALL
	F	A023	2	W1104	575	16		33-21-31	155-156
	F	A023	2	W1104	802	16		33-21-31	155-156
	F	A025	2	W1058	209B	24		21-61-71	ALL
	F	A025	2	W1060	247B	24		21-61-71	ALL
	F	A027	2	W1058	210B	24		21-61-71	ALL
	F	A027	2	W1060	248B	24		21-61-71	ALL
	X	B005	BJ	W1060	720	24		33-21-11	050-099, 150-199
	X	B005	BJ	W1104	647	24		33-21-11	050-099, 150-199
	X	C005	BJ	W1060	535	24		33-21-11	050-099, 150-199
	X	C005	BJ	W1104	648	24		33-21-11	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 253

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0160		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0160		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0160	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Y	C012	BJ	W1060	140	20		33-51-21	ALL
	Y	C012	BJ	W1060	141	20		33-51-21	ALL
	Y	C012	BJ	W1060	153	20		33-51-21	ALL
	Y	C013	BJ	W1060	155	22		33-51-21	ALL
	Y	C013	BJ	W1060	159	22		33-51-21	ALL
	Y	C013	BJ	W1104	108	22		33-51-21	ALL
	Y	C014	BJ	W1060	110	22		33-51-11	275-299
	Y	C014	BJ	W1060	570	22		33-51-11	ALL
	Y	C014	BJ	W1110	073	22		33-51-11	ALL
	Y	C015	BJ	W1060	046	22		33-22-41	ALL
	Y	C015	BJ	W1060	631	22		33-22-41	ALL
	Y	C015	BJ	W1060	632	22		33-22-41	ALL
	Y	C016	BJ	W1060	047	22		33-22-41	275-299
	Y	C016	BJ	W1060	050	22		33-22-41	ALL
	Y	C016	BJ	W1060	052	22		33-22-41	ALL
	Y	C016	BJ	W1060	690	22		33-22-41	050-099, 150-199
	Y	C016	BJ	W1104	738	22		33-22-41	050-099, 150-199
	Y	C017	BJ	W1058	031	20		33-26-21	050-099, 150-157
	Y	C017	BJ	W1058	032	20		33-26-21	280-299
	Y	C017	BJ	W1058	038	20		33-26-21	162-199
	Y	C017	BJ	W1060	620	20		33-26-21	162-199
	Y	C017	BJ	W1060	620	22		33-26-21	280-299
	Y	C017	BJ	W1060	823	20		33-26-21	162-199
	Y	C017	BJ	W1102	105	20		33-26-21	050-099, 150-157
	Y	C017	BJ	W1104	788	20		33-26-21	050-099
	Y	C017	BJ	W1104	794	20		33-26-21	050-099
	Y	C017	BJ	W1104	874	20		33-26-21	280-299
	F	C021	2	W1058	211R	20		21-65-11	ALL
	F	C021	2	W1060	249R	20		21-65-11	ALL
	F	C023	2	W1060	588	20		27-61-18	ALL
	F	C023	2	W1104	023	20		27-61-18	ALL
	F	C025	2	W1058	209R	24		21-61-71	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 254

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0160		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0160		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0160	F	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	G	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	H	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	X	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	Y	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0160	Z	<b>BACM15C3C (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	F	C025	2	W1060	247R	24		21-61-71	ALL
	F	C027	2	W1058	210R	24		21-61-71	ALL
	F	C027	2	W1060	248R	24		21-61-71	ALL
	F	C038	2	W1060	589	20		27-61-18	ALL
	F	C038	2	W1104	020	20		27-61-18	ALL
	X	D005	BJ	W1060	733	24		33-21-11	050-099, 150-199
	X	D005	BJ	W1104	720	24		33-21-11	050-099, 150-199
	F	DED		W1104	802Z			33-21-31	155-156
	H	DED		W1110	088Z			33-51-11	ALL
<b>TB0161</b>		<b>284T0338</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
<b>TB0161</b>	F	<b>BACM15C1A</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
<b>TB0161</b>	G	<b>BACM15C1B</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
<b>TB0161</b>	H	<b>BACM15C2A</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
	G	1	2	W0161	213R	24		34-61-12	ALL
	G	1	2	W0161	214R	24		32-42-11	ALL
	G	1	2	W0161	222R	24		34-46-11	ALL
	G	1	2	W0161	223R	24		34-21-11	ALL
	G	10	2	W0161	022	22		34-21-11	ALL
	G	10	2	W0161	038	22		22-21-11	ALL
	G	11	2	W0161	201R	24		34-21-11	ALL
	G	11	2	W0161	203R	24		34-21-11	ALL
	G	12	2	W0161	201B	24		34-21-11	ALL
	G	12	2	W0161	203B	24		34-21-11	ALL
	G	13	2	W0161	210R	24		34-21-11	ALL
	G	13	2	W0161	215R	24		34-22-38	ALL
	G	13	2	W0161	218R	24		34-22-18	ALL
	G	13	2	W0161	220R	24		22-21-11	ALL
	G	14	2	W0161	210B	24		34-21-11	ALL
	G	14	2	W0161	215B	24		34-22-38	ALL
	G	14	2	W0161	218B	24		34-22-18	ALL
	G	14	2	W0161	220B	24		22-21-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 255

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0161		<b>284T0338 (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
	G	15	2	W0181	213R	24		34-61-12	ALL
	G	15	2	W0181	221R	24		34-21-31	ALL
	G	16	2	W0181	213B	24		34-61-12	ALL
	G	16	2	W0181	221B	24		34-21-31	ALL
	G	17	2	W0171	209R	24		22-13-21	ALL
	G	17	2	W0171	225R	24		34-21-21	ALL
	G	17	2	W0171	227R	24		22-21-11	ALL
	G	18	2	W0171	209B	24		22-13-21	ALL
	G	18	2	W0171	225B	24		34-21-21	ALL
	G	18	2	W0171	227B	24		22-21-11	ALL
	G	19	2	W0161	205R	24		34-21-11	ALL
	G	19	2	W0161	206R	24		34-21-11	ALL
	G	19	2	W0181	205R	24		34-21-31	ALL
	G	2	2	W0161	213B	24		34-61-12	ALL
	G	2	2	W0161	214B	24		32-42-11	ALL
	G	2	2	W0161	222B	24		34-46-11	ALL
	G	2	2	W0161	223B	24		34-21-11	ALL
	G	20	2	W0161	205B	24		34-21-11	ALL
	G	20	2	W0161	206B	24		34-21-11	ALL
	G	20	2	W0181	205B	24		34-21-31	ALL
	G	21	2	W0161	217R	24		34-61-15	ALL
	G	21	2	W0171	207R	24		34-21-21	ALL
	G	21	2	W0181	207R	24		34-21-31	ALL
	G	22	2	W0161	217B	24		34-61-15	ALL
	G	22	2	W0171	207B	24		34-21-21	ALL
	G	22	2	W0181	207B	24		34-21-31	ALL
	G	24	2	W0161	208R	24		34-21-11	ALL
	G	24	2	W0171	217R	24		34-61-25	ALL
	G	24	2	W0181	208R	24		34-21-31	ALL
	G	25	2	W0161	208B	24		34-21-11	ALL
	G	25	2	W0171	217B	24		34-61-25	ALL
	G	25	2	W0181	208B	24		34-21-31	ALL
	G	26	2	W0161	216R	24		34-21-11	ALL
	G	26	2	W0171	228R	24		34-21-31	ALL
	G	26	2	W0181	219R	24		34-21-31	ALL
	G	27	2	W0161	216B	24		34-21-11	ALL
	G	27	2	W0171	228B	24		34-21-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 256

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0161		<b>284T0338 (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
	G	27	2	W0181	219B	24		34-21-31	ALL
	G	29	2	W0181	211R	24		34-21-31	ALL
	G	29	2	W0181	212R	24		34-22-18	ALL
	G	29	2	W0181	215R	24		34-22-28	ALL
	H	3	2	W0161	202R	24		34-21-11	ALL
	H	3	2	W0161	204R	24		34-21-11	ALL
	H	3	2	W0161	211R	24		34-22-91	ALL
	H	3	2	W0161	212R	24		22-32-11	ALL
	H	3	2	W0161	223R	24		34-21-11	ALL
	H	3	2	W0161	228R	22		23-25-13	150, 153-155, 162-165
	H	3	2	W0161	228R	24		23-25-13	156-157, 166-199, 277-299
	G	30	2	W0181	211B	24		34-21-31	ALL
	G	30	2	W0181	212B	24		34-22-18	ALL
	G	30	2	W0181	215B	24		34-22-28	ALL
	H	31	2	W0181	202R	24		34-21-31	ALL
	H	31	2	W0181	204R	24		34-21-31	ALL
	H	31	2	W0181	210R	24		34-22-81	ALL
	H	31	2	W0181	214R	24		34-43-11	ALL
	H	31	2	W0181	217R	24		32-42-11	ALL
	H	31	2	W0181	220R	24		22-21-11	ALL
	H	31	2	W0181	221R	24		34-21-31	ALL
	H	33	2	W0181	202B	24		34-21-31	ALL
	H	33	2	W0181	204B	24		34-21-31	ALL
	H	33	2	W0181	210B	24		34-22-81	ALL
	H	33	2	W0181	214B	24		34-43-11	ALL
	H	33	2	W0181	217B	24		32-42-11	ALL
	H	33	2	W0181	220B	24		22-21-11	ALL
	H	33	2	W0181	221B	24		34-21-31	ALL
	G	35	2	W0181	015	22		34-21-31	ALL
	G	35	2	W0181	018	22		34-21-31	ALL
	G	35	2	W0181	053	22		34-21-31	ALL
	G	36	2	W0181	016	22		34-21-31	ALL
	G	36	2	W0181	019	22		34-21-31	ALL
	G	36	2	W0181	054	22		34-21-31	ALL
	G	37	2	W0181	017	22		34-21-31	ALL
	G	37	2	W0181	020	22		34-21-31	ALL
	G	37	2	W0181	055	22		34-21-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 257

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0161		<b>284T0338 (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
	G	38	2	W0181	022	22		34-21-31	ALL
	G	38	2	W0181	038	22		22-21-11	ALL
	G	39	2	W0181	201R	24		34-21-31	ALL
	G	39	2	W0181	203R	24		34-21-31	ALL
	G	40	2	W0181	201B	24		34-21-31	ALL
	G	40	2	W0181	203B	24		34-21-31	ALL
	G	41	2	W0171	218R	24		34-22-28	ALL
	G	41	2	W0171	221R	24		22-21-21	ALL
	G	41	2	W0171	226R	24		34-21-21	ALL
	G	44	2	W0161	036	24		34-21-11	ALL
	G	44	2	W0161	101	24		34-21-11	ALL
	G	44	2	W0181	101	24		34-22-37	ALL
	G	44	2	W0181	102	24		34-22-17	ALL
	G	45	2	W0171	218B	24		34-22-28	ALL
	G	45	2	W0171	221B	24		22-21-21	ALL
	G	45	2	W0171	226B	24		34-21-21	ALL
	G	46	2	W0171	213R	24		34-61-22	ALL
	G	46	2	W0171	214R	24		32-42-11	ALL
	G	46	2	W0171	222R	24		34-21-21	ALL
	G	47	2	W0171	213B	24		34-61-22	ALL
	G	47	2	W0171	214B	24		32-42-11	ALL
	G	47	2	W0171	222B	24		34-21-21	ALL
	H	48	2	W0171	202R	24		34-21-21	ALL
	H	48	2	W0171	204R	24		34-21-21	ALL
	H	48	2	W0171	206R	24		34-43-21	ALL
	H	48	2	W0171	210R	24		34-22-81	ALL
	H	48	2	W0171	212R	24		22-32-11	ALL
	H	48	2	W0171	222R	24		34-21-21	ALL
	H	48	2	W0171	229R	22		23-25-13	150, 153-155, 162-165
	H	48	2	W0171	229R	24		23-25-13	156-157, 166-199, 277-299
	H	5	2	W0161	202B	24		34-21-11	ALL
	H	5	2	W0161	204B	24		34-21-11	ALL
	H	5	2	W0161	211B	24		34-22-91	ALL
	H	5	2	W0161	212B	24		22-32-11	ALL
	H	5	2	W0161	223B	24		34-21-11	ALL
	H	5	2	W0161	228B	22		23-25-13	150, 153-155, 162-165
	H	5	2	W0161	228B	24		23-25-13	156-157, 166-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 258

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0161		<b>284T0338 (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
	H	50	2	W0171	202B	24		34-21-21	ALL
	H	50	2	W0171	204B	24		34-21-21	ALL
	H	50	2	W0171	206B	24		34-43-21	ALL
	H	50	2	W0171	210B	24		34-22-81	ALL
	H	50	2	W0171	212B	24		22-32-11	ALL
	H	50	2	W0171	222B	24		34-21-21	ALL
	H	50	2	W0171	229B	22		23-25-13	150, 153-155, 162-165
	H	50	2	W0171	229B	24		23-25-13	156-157, 166-199, 277-299
	G	52	2	W0171	015	22		34-21-21	ALL
	G	52	2	W0171	018	22		34-21-21	ALL
	G	52	2	W0171	053	22		34-21-21	ALL
	G	53	2	W0171	016	22		34-21-21	ALL
	G	53	2	W0171	019	22		34-21-21	ALL
	G	53	2	W0171	054	22		34-21-21	ALL
	G	54	2	W0171	017	22		34-21-21	ALL
	G	54	2	W0171	020	22		34-21-21	ALL
	G	54	2	W0171	055	22		34-21-21	ALL
	G	55	2	W0171	002	22		22-21-21	ALL
	G	55	2	W0171	022	22		34-21-21	ALL
	G	56	2	W0171	201R	24		34-21-21	ALL
	G	56	2	W0171	203R	24		34-21-21	ALL
	G	57	2	W0171	201B	24		34-21-21	ALL
	G	57	2	W0171	203B	24		34-21-21	ALL
	G	59	2	W0171	205B	24		34-21-21	ALL
	G	59	2	W0171	219B	24		34-21-21	ALL
	G	59	2	W0171	233B	24		34-22-29	ALL
	G	60	2	W0171	205R	24		34-21-21	ALL
	G	60	2	W0171	219R	24		34-21-21	ALL
	G	60	2	W0171	233R	24		34-22-29	ALL
	G	61	2	W0161	209R	24		34-21-11	ALL
	G	61	2	W0161	225R	24		22-13-11	ALL
	G	61	2	W0161	226R	24		22-21-21	ALL
	G	62	2	W0161	209B	24		34-21-11	ALL
	G	62	2	W0161	225B	24		22-13-11	ALL
	G	62	2	W0161	226B	24		22-21-21	ALL
	G	7	2	W0161	015	22		34-21-11	ALL
	G	7	2	W0161	018	22		34-21-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 259

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0161		<b>284T0338 (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
TB0161	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>SHELF/E01/06</b>		<b>ALL</b>
	G	7	2	W0161	023	22		34-21-11	ALL
	G	8	2	W0161	016	22		34-21-11	ALL
	G	8	2	W0161	019	22		34-21-11	ALL
	G	8	2	W0161	024	22		34-21-11	ALL
	G	9	2	W0161	017	22		34-21-11	ALL
	G	9	2	W0161	020	22		34-21-11	ALL
	G	9	2	W0161	025	22		34-21-11	ALL
	F	A023	2	W0161	227R	24		34-21-21	ALL
	F	A023	2	W0171	216R	24		34-21-21	ALL
	F	A058	2	W0171	208B	24		34-21-21	ALL
	F	A058	2	W0171	224B	24		34-21-21	ALL
	F	C023	2	W0161	227B	24		34-21-21	ALL
	F	C023	2	W0171	216B	24		34-21-21	ALL
	F	C058	2	W0171	208R	24		34-21-21	ALL
	F	C058	2	W0171	224R	24		34-21-21	ALL
	H	DED		W0161	223Z			34-21-11	ALL
	H	DED		W0171	222Z			34-21-21	ALL
	H	DED		W0181	221Z			34-21-31	ALL
<b>TB0162</b>		<b>BACT44B1350U</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0162</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0162</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0162</b>	<b>H</b>	<b>BACM15C2A</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0162</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0162</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P025-00/ /</b>		<b>ALL</b>
<b>TB0162</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P025-00/ /</b>		<b>ALL</b>
	G	1	2	W1108	005	20		33-21-12	ALL
	G	1	2	W1108	006	20		33-21-12	ALL
	G	1	2	W1108	007	20		33-21-12	275-299
	G	1	2	W1108	008	20		33-21-12	ALL
	Z	10	BJ	W1064	030	22		33-51-11	ALL
	Z	10	BJ	W1064	044	22		33-51-11	ALL
	Z	10	BJ	W1064	045	22		33-51-11	ALL
	Z	10	BJ	W1064	047	22		33-51-11	ALL
	Z	10	BJ	W1064	057	22		33-51-11	ALL
	Z	17	BJ	W1108	010	24		33-21-12	ALL
	Z	17	BJ	W1108	016	24		33-21-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 260

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0162		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	F	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	G	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	H	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	X	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	Y	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	Z	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	Z	17	BJ	W1108	022	24		33-21-12	ALL
	Z	17	BJ	W1108	093	24		33-21-12	ALL
	Z	17	BJ	W1108	140	24		33-21-12	ALL
	Z	18	BJ	W1064	077	20		33-22-42	275-299
	Z	18	BJ	W1064	503	22		33-22-42	275-299
	Z	18	BJ	W1064	506	22		33-22-42	275-299
	Z	18	BJ	W1064	510	22		33-22-42	275-299
	G	2	2	W1108	013	20		33-21-12	ALL
	G	2	2	W1108	018	20		33-21-12	ALL
	G	2	2	W1108	019	20		33-21-12	275-299
	G	2	2	W1108	020	20		33-21-12	ALL
	G	3	2	W1064	001	24		33-21-12	ALL
	G	3	2	W1108	015	24		33-21-12	ALL
	G	3	2	W1108	030	24		33-21-12	275-299
	H	32	2	W1064	016	18		33-22-11	ALL
	H	32	2	W1064	017	18		33-22-11	ALL
	H	32	2	W1064	024	18		33-22-31	050-099, 150-199, 275-278
	H	32	2	W1064	026	18		33-27-11	150-199
	H	32	2	W1064	026	18		33-22-31	275-299
	H	32	2	W1064	619	18		33-27-11	150-199
	H	32	2	W1064	632	18		33-22-31	050-099, 150-199
	H	32	2	W1108	657	24		33-21-31	050-099, 162-199
	H	32	2	W1108	662	24		33-21-31	050-099, 162-199
	Z	35	BJ	W1064	029	22		33-51-11	ALL
	Z	35	BJ	W1064	052	22		33-51-11	ALL
	Z	35	BJ	W1064	058	22		33-51-11	ALL
	Z	35	BJ	W1064	059	22		33-51-11	ALL
	Z	35	BJ	W1064	060	22		33-51-11	ALL
	Z	35	BJ	W1064	061	22		33-51-11	ALL
	Z	37	BJ	W1064	078	22		33-22-42	275-299
	Z	37	BJ	W1064	079	22		33-22-42	275-299
	Z	37	BJ	W1064	088	22		33-22-42	275-299
	Z	37	BJ	W1064	507	22		33-22-42	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 261

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0162		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	F	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	G	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	H	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	X	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	Y	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	Z	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	Z	37	BJ	W1064	700	22		33-22-42	275-299
	Z	38	BJ	W1064	088	22		33-22-42	150-199, 275-299
	Z	38	BJ	W1064	089	22		33-22-42	150-199, 275-299
	Z	38	BJ	W1064	090	22		33-22-42	ALL
	Z	38	BJ	W1064	091	22		33-22-42	050-099
	Z	38	BJ	W1064	093	22		33-22-42	151, 275-299
	Z	38	BJ	W1064	094	22		33-22-42	150-199, 275-299
	Z	38	BJ	W1064	139	22		33-22-42	050-099
	Z	38	BJ	W1064	550	22		33-22-42	050-099
	Z	38	BJ	W1064	612	20		33-22-42	050-099
	Z	38	BJ	W1064	655	22		33-22-42	280-299
	Z	38	BJ	W1108	646	22		33-22-42	151
	Z	39	BJ	W1106	112	22		38-32-12	050-099, 150-156, 162-165, 275-276
	Z	39	BJ	W1106	112	22		38-32-16	157, 166-199, 277-299
	Z	39	BJ	W1106	113	22		38-32-12	050-099, 150-156, 162-165, 275-276
	Z	39	BJ	W1106	113	22		38-32-16	157, 166-199, 277-299
	Z	39	BJ	W1106	114	22		SPARE	150-154
	Z	39	BJ	W1106	114	22		38-32-12	275-276
	Z	39	BJ	W1106	114	22		38-32-16	277-299
	Z	39	BJ	W1108	150	20		38-32-12	050-099, 150-156, 162-165
	Z	39	BJ	W1108	150	20		38-32-16	157, 166-199
	G	4	2	W1064	106	22		33-27-11	275-299
	G	4	2	W1064	567	22		21-66-31	050-099, 150, 152-199
	G	4	2	W1108	063	22		33-27-11	275-299
	G	4	2	W1108	503	22		33-27-11	275-299
	G	4	2	W1108	533	22		21-66-31	050-099, 150, 152-199
	Z	40	BJ	W1064	096	22		33-22-42	275-299
	Z	40	BJ	W1064	505	22		33-22-42	275-299
	Z	40	BJ	W1108	054	22		33-22-42	275-299
	G	5	2	W1064	641	22		21-66-41	050-099, 150, 152-199
	G	5	2	W1108	535	22		21-66-41	050-099, 150, 152-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 262

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0162		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	F	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	G	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	H	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	X	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	Y	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	Z	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	G	6	2	W1064	568	22		21-66-41	050-099, 150, 152-199
	G	6	2	W1108	534	22		21-66-41	050-099, 150, 152-199
	G	7	2	W1064	002	24		33-21-12	ALL
	G	7	2	W1064	083	22		33-22-42	050-099, 150-199
	G	7	2	W1064	627	24		33-21-31	050-099, 150-199
	G	7	2	W1108	017	24		33-21-12	275-299
	G	7	2	W1108	023	24		33-21-12	ALL
	G	8	2	W1064	618	18		33-27-11	150-199
	G	8	2	W1108	159	18		33-27-11	150-199
	Z	9	BJ	W1064	105	22		33-27-11	ALL
	Z	9	BJ	W1064	109	22		33-27-11	ALL
	Z	9	BJ	W1064	110	22		33-27-11	ALL
	Z	9	BJ	W1064	113	22		33-27-11	ALL
	Z	9	BJ	W1064	116	22		33-27-11	ALL
	Y	A011	BJ	W1064	025	20		33-51-11	ALL
	Y	A011	BJ	W1064	055	20		33-51-11	ALL
	Y	A011	BJ	W1064	056	20		33-51-11	ALL
	Y	A012	BJ	W1064	062	20		33-51-11	ALL
	Y	A012	BJ	W1064	067	20		33-51-11	ALL
	Y	A012	BJ	W1064	068	20		33-51-11	ALL
	Y	A016	BJ	W1064	107	20		33-27-11	ALL
	Y	A016	BJ	W1064	115	20		33-27-11	ALL
	Y	A016	BJ	W1108	060	20		33-27-11	ALL
	Y	A019	BJ	W1064	088	22		33-22-42	050-099
	Y	A019	BJ	W1064	089	22		33-22-42	050-099
	Y	A019	BJ	W1064	091	22		33-22-42	150-199
	Y	A019	BJ	W1064	094	22		33-22-42	050-099
	Y	A019	BJ	W1064	139	22		33-22-42	150-199
	Y	A019	BJ	W1064	550	22		33-22-42	150-199
	Y	A019	BJ	W1064	612	20		33-22-42	150-199
	F	A021	2	W1064	211R	22		23-31-14	ALL
	F	A021	2	W1108	201R	22		23-31-14	ALL
	X	A023	BJ	W1064	086	22		33-22-42	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 263

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0162		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	X	A023	BJ	W1108	051	22		33-22-42	275-299
	X	A025	BJ	W1064	163	22		33-51-11	ALL
	X	A025	BJ	W1108	095	22		33-51-11	ALL
	X	A026	BJ	W1064	112	20		33-27-11	ALL
	X	A026	BJ	W1108	061	20		33-27-11	ALL
	Y	A029	BJ	W1064	031	20		33-24-14	050-099
	Y	A029	BJ	W1064	120	20		33-24-14	050-099
	Y	A029	BJ	W1064	121	20		33-24-14	050-099
	Y	A030	BJ	W1106	140	20		33-24-11	275-299
	Y	A030	BJ	W1108	038	20		33-24-11	275-299
	Y	A030	BJ	W1108	049	20		33-24-11	275-299
	X	B023	BJ	W1064	092	22		33-22-42	050-099
	X	B023	BJ	W1108	053	22		33-22-42	050-099
	X	B026	BJ	W1064	114	22		33-27-11	ALL
	X	B026	BJ	W1108	062	22		33-27-11	ALL
	Y	C012	BJ	W1064	092	22		33-22-42	150-199, 275-299
	Y	C012	BJ	W1108	053	22		33-22-42	150-199, 275-299
	Y	C013	BJ	W1064	077	20		33-22-42	050-099, 150-199
	Y	C013	BJ	W1064	503	22		33-22-42	050-099, 150-199
	Y	C013	BJ	W1064	506	22		33-22-42	050-099, 150-199
	Y	C013	BJ	W1064	901	22		33-22-42	150, 152-199
	Y	C014	BJ	W1064	003	22		33-21-21	ALL
	Y	C014	BJ	W1064	005	24		33-21-21	ALL
	Y	C014	BJ	W1064	512	22		33-21-21	ALL
	Y	C015	BJ	W1106	141	22		33-26-11	150-199, 275-299
	Y	C015	BJ	W1108	043	22		33-26-11	150-199
	Y	C015	BJ	W1108	043	20		33-26-11	275-299
	Y	C015	BJ	W1108	058	22		33-26-11	275-299
	Y	C016	BJ	W1064	080	22		33-22-42	050-099
	Y	C016	BJ	W1064	080	20		33-22-42	150-199
	Y	C016	BJ	W1064	504	22		33-22-42	275-299
	Y	C016	BJ	W1064	505	22		33-22-42	050-099, 150-199
	Y	C016	BJ	W1064	654	22		33-22-42	280-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 264

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0162		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	F	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	G	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	H	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	X	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	Y	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	Z	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	Y	C016	BJ	W1064	704	22		33-22-42	275-299
	Y	C016	BJ	W1064	705	22		33-22-42	275-278
	Y	C016	BJ	W1108	052	22		33-22-42	050-099
	Y	C016	BJ	W1108	052	20		33-22-42	150-199
	Y	C019	BJ	W1064	087	22		33-22-42	275-278
	Y	C019	BJ	W1064	652	22		33-22-42	280-299
	Y	C019	BJ	W1064	703	22		33-22-42	275-299
	Y	C019	BJ	W1108	050	22		33-22-42	275-299
	Y	C020	BJ	W1064	601	22		30-46-11	ALL
	Y	C020	BJ	W1064	602	22		30-46-11	ALL
	Y	C020	BJ	W1064	603	22		30-46-11	ALL
	F	C021	2	W1064	211B	22		23-31-14	ALL
	F	C021	2	W1108	201B	22		23-31-14	ALL
	X	C023	BJ	W1064	080	22		33-22-42	275-299
	X	C023	BJ	W1108	052	22		33-22-42	275-299
	X	C026	BJ	W1064	108	20		33-27-11	ALL
	X	C026	BJ	W1108	064	20		33-27-11	ALL
	Y	C028	BJ	W1108	656	20		33-21-31	050-099
	Y	C028	BJ	W1108	661	20		33-21-31	050-099
	Y	C028	BJ	W1108	674	20		33-21-31	050-099
	Y	C029	BJ	W1064	032	20		33-24-14	050-099
	Y	C029	BJ	W1064	122	20		33-24-14	050-099
	Y	C029	BJ	W1064	123	20		33-24-14	050-099
	Y	C030	BJ	W1108	508	20		33-21-31	162-199
	Y	C030	BJ	W1108	531	20		33-21-31	162-199
	Y	C030	BJ	W1108	532	20		33-21-31	162-199
	X	D022	BJ	W1064	630	24		33-21-12	050-099
	X	D022	BJ	W1108	189	24		33-21-12	050-099
	X	D023	BJ	W1064	500	22		33-22-42	050-099
	X	D023	BJ	W1108	056	22		33-22-42	050-099
	X	D026	BJ	W1064	106	22		33-27-11	050-099, 150-199
	X	D026	BJ	W1108	063	22		33-27-11	050-099, 150-199
	Y	DED		W1064	107Z			33-27-11	050-099

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 265

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0162		<b>BACT44B1350U (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
TB0162	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P025-00/ /</b>		<b>ALL</b>
	X	DED		W1064	108Z			33-27-11	050-099
	X	DED		W1064	112Z			33-27-11	050-099
	Y	DED		W1064	115Z			33-27-11	050-099
<b>TB0163</b>		<b>284T0116-4</b>					<b>SHELF/E02/06</b>		<b>ALL</b>
<b>TB0163</b>	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E02/06</b>		<b>ALL</b>
	F	10	2	W0163	052R	22		23-25-14	150, 153-199
	F	10	2	W0163	952R	22		23-25-14	150, 153-199
	F	11	2	W0163	052B	22		23-25-14	150, 153-199
	F	11	2	W0163	952B	22		23-25-14	150, 153-199
	F	12	BJ	W0173	054R	22		23-25-14	150, 153-199
	F	12	BJ	W0173	954R	22		23-25-14	150, 153-199
	F	13	BJ	W0173	054B	22		23-25-14	150, 153-199
	F	13	BJ	W0173	954B	22		23-25-14	150, 153-199
	G	14	2	W0163	061	22		23-25-14	150, 153-155, 162-165
	G	14	2	W0163	061	24		23-25-14	156-157, 166-199, 277-299
	G	14	2	W0163	063	22		23-25-14	150, 153-155, 162-165
	G	14	2	W0163	063	24		23-25-14	156-157, 166-199, 277-299
	G	14	2	W0173	059	22		23-25-14	150, 153-155, 162-165
	G	14	2	W0173	059	24		23-25-14	156-157, 166-199, 277-299
	G	16	2	W0173	052	24		23-25-14	277-299
	G	16	2	W0173	060	22		23-25-14	150, 153-155, 162-165
	G	16	2	W0173	060	24		23-25-14	156-157, 166-199, 277-299
	G	16	2	W0173	061	22		23-25-14	150, 153-155, 162-165
	G	16	2	W0173	061	24		23-25-14	156-157, 166-199, 277-299
	G	18	2	W0163	049	22		23-25-14	150, 153-155, 162-165
	G	18	2	W0163	049	24		23-25-14	277-299
	G	18	2	W0163	066	22		23-25-14	150, 153-155, 162-165
	G	18	2	W0163	066	24		23-25-14	156-157, 166-199, 277-299
	G	18	2	W0163	067	22		23-25-14	150, 153-155, 162-165
	G	18	2	W0163	067	24		23-25-14	156-157, 166-199, 277-299
	G	70	2	W0163	010	20		23-11-11	ALL
	G	70	2	W0163	011	20		23-11-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 266

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0163</b>		<b>284T0116-4 (continued)</b>					<b>SHELF/E02/06</b>		<b>ALL</b>
<b>TB0163</b>	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E02/06</b>		<b>ALL</b>
	G	70	2	W0163	016	22		23-11-11	ALL
	G	74	2	W0173	010	20		23-11-21	ALL
	G	74	2	W0173	011	20		23-11-21	ALL
	G	74	2	W0173	016	22		23-11-21	ALL
	G	DED		W0163	010Z			23-11-11	ALL
	G	DED		W0163	011Z			23-11-11	ALL
	G	DED		W0163	016Z			23-11-11	ALL
	G	DED		W0173	010Z			23-11-21	ALL
	G	DED		W0173	011Z			23-11-21	ALL
	G	DED		W0173	016Z			23-11-21	ALL
	F	REF		W0163	052	20		23-25-14	150, 153-199
	F	REF		W0163	052Z			23-25-14	150, 153-199
	F	REF		W0163	952	20		23-25-14	150, 153-199
	F	REF		W0163	952Z			23-25-14	150, 153-199
	F	REF		W0173	054	20		23-25-14	150, 153-199
	F	REF		W0173	054Z			23-25-14	150, 153-199
	F	REF		W0173	954	20		23-25-14	150, 153-199
	F	REF		W0173	954Z			23-25-14	150, 153-199
<b>TB0164</b>		<b>284T0603</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
<b>TB0164</b>	<b>F</b>	<b>BACM15C1A</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
<b>TB0164</b>	<b>X</b>	<b>BACM15C3A</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
<b>TB0164</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
	F	A001	2	W0082	207R	24		21-61-11	ALL
	F	A001	2	W0084	206R	24		21-61-11	ALL
	F	A002	2	W0082	208R	24		21-61-11	ALL
	F	A002	2	W0084	207R	24		21-61-11	ALL
	F	A003	2	W0082	309B	24		21-61-11	ALL
	F	A003	2	W0084	309B	24		21-61-11	ALL
	F	A004	2	W0082	309Y	24		21-61-11	ALL
	F	A004	2	W0084	309Y	24		21-61-11	ALL
	F	A005	2	W0082	310R	24		21-61-21	ALL
	F	A005	2	W0084	310R	24		21-61-21	ALL
	X	A006	BJ	W0082	209B	24		21-61-21	ALL
	X	A006	BJ	W0084	209B	24		21-61-21	ALL
	X	A007	BJ	W0082	150	24		21-61-41	ALL
	X	A007	BJ	W0084	145	24		21-61-41	ALL
	F	A008	2	W0082	134	24		21-61-41	ALL
	F	A008	2	W0084	120	24		21-61-41	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 267

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0164		<b>284T0603 (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0164	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0164	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0164	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
	F	A009	2	W0082	311B	24		21-61-31	ALL
	F	A009	2	W0084	312B	24		21-61-31	ALL
	F	A010	2	W0082	311Y	24		21-61-31	ALL
	F	A010	2	W0084	312Y	24		21-61-31	ALL
	X	A011	BJ	W0082	212B	24		21-61-51	ALL
	X	A011	BJ	W0084	219B	24		21-61-51	ALL
	X	A012	BJ	W0082	213B	24		21-61-51	ALL
	X	A012	BJ	W0084	220B	24		21-61-51	ALL
	Y	A013	BJ	W0082	237B	24		21-61-51	ALL
	Y	A013	BJ	W0084	223B	24		21-61-51	ALL
	Y	A013	BJ	W0084	241B	24		21-61-51	ALL
	Y	A014	BJ	W0082	215B	24		21-61-51	ALL
	Y	A014	BJ	W0082	236B	24		21-61-51	ALL
	Y	A014	BJ	W0084	215B	24		21-61-51	ALL
	F	A015	2	W0082	216B	24		21-61-51	ALL
	F	A015	2	W0084	216B	24		21-61-51	ALL
	F	A016	2	W0082	229R	24		21-51-12	ALL
	F	A016	2	W0084	235R	24		21-51-22	ALL
	F	A017	2	W0082	230R	24		21-51-12	ALL
	F	A017	2	W0084	236R	24		21-51-22	ALL
	X	B006	BJ	W0082	209R	24		21-61-21	ALL
	X	B006	BJ	W0084	209R	24		21-61-21	ALL
	X	B007	BJ	W0082	151	24		21-61-41	ALL
	X	B007	BJ	W0084	146	24		21-61-41	ALL
	X	B011	BJ	W0082	212R	24		21-61-51	ALL
	X	B011	BJ	W0084	219R	24		21-61-51	ALL
	X	B012	BJ	W0082	213R	24		21-61-51	ALL
	X	B012	BJ	W0084	220R	24		21-61-51	ALL
	F	C001	2	W0082	207B	24		21-61-11	ALL
	F	C001	2	W0084	206B	24		21-61-11	ALL
	F	C002	2	W0082	208B	24		21-61-11	ALL
	F	C002	2	W0084	207B	24		21-61-11	ALL
	F	C003	2	W0082	309R	24		21-61-11	ALL
	F	C003	2	W0084	309R	24		21-61-11	ALL
	F	C004	2	W0082	310B	24		21-61-21	ALL
	F	C004	2	W0084	310B	24		21-61-21	ALL
	F	C005	2	W0082	310Y	24		21-61-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 268

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0164		<b>284T0603 (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0164	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0164	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0164	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
	F	C005	2	W0084	310Y	24		21-61-21	ALL
	X	C006	BJ	W0082	210B	24		21-61-21	ALL
	X	C006	BJ	W0084	210B	24		21-61-21	ALL
	F	C008	2	W0082	133	24		21-61-41	ALL
	F	C008	2	W0084	119	24		21-61-41	ALL
	F	C009	2	W0082	311R	24		21-61-31	ALL
	F	C009	2	W0084	312R	24		21-61-31	ALL
	F	C010	2	W0082	069	24		21-61-51	ALL
	F	C010	2	W0084	035	18		21-61-51	ALL
	X	C012	BJ	W0082	214B	24		21-61-51	ALL
	X	C012	BJ	W0084	228B	24		21-61-51	ALL
	Y	C013	BJ	W0082	237R	24		21-61-51	ALL
	Y	C013	BJ	W0084	223R	24		21-61-51	ALL
	Y	C013	BJ	W0084	241R	24		21-61-51	ALL
	Y	C014	BJ	W0082	215R	24		21-61-51	ALL
	Y	C014	BJ	W0082	236R	24		21-61-51	ALL
	Y	C014	BJ	W0084	215R	24		21-61-51	ALL
	F	C015	2	W0082	216R	24		21-61-51	ALL
	F	C015	2	W0084	216R	24		21-61-51	ALL
	F	C016	2	W0082	229B	24		21-51-12	ALL
	F	C016	2	W0084	235B	24		21-51-22	ALL
	F	C017	2	W0082	230B	24		21-51-12	ALL
	F	C017	2	W0084	236B	24		21-51-22	ALL
	X	D006	BJ	W0082	210R	24		21-61-21	ALL
	X	D006	BJ	W0084	210R	24		21-61-21	ALL
	X	D012	BJ	W0082	214R	24		21-61-51	ALL
	X	D012	BJ	W0084	228R	24		21-61-51	ALL
	F	DED		W0084	035Z			21-61-51	ALL
<b>TB0165</b>		<b>284T0151</b>					<b>SHELF/E05/01</b>		<b>ALL</b>
<b>TB0165</b>	<b>F</b>	<b>BACM15C1A</b>					<b>SHELF/E05/01</b>		<b>ALL</b>
<b>TB0165</b>	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E05/01</b>		<b>ALL</b>
<b>TB0165</b>	<b>X</b>	<b>BACM15C3A</b>					<b>SHELF/E05/01</b>		<b>ALL</b>
<b>TB0165</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>SHELF/E05/01</b>		<b>ALL</b>
<b>TB0165</b>	<b>Z</b>	<b>BACM15C3B</b>					<b>SHELF/E05/01</b>		<b>ALL</b>
	G	10	2	W0175	031	24		34-57-21	ALL
	G	10	2	W0175	032	24		34-57-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 269

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0165		284T0151 (continued)					SHELF/E05/01		ALL
TB0165	F	BACM15C1A (continued)					SHELF/E05/01		ALL
TB0165	G	BACM15C1B (continued)					SHELF/E05/01		ALL
TB0165	X	BACM15C3A (continued)					SHELF/E05/01		ALL
TB0165	Y	BACM15C3B (continued)					SHELF/E05/01		ALL
TB0165	Z	BACM15C3B (continued)					SHELF/E05/01		ALL
	G	10	2	W0175	033	24		34-57-21	ALL
	G	17	2	W0175	229R	24		34-22-18	ALL
	G	17	2	W0175	230R	24		34-22-91	ALL
	G	17	2	W0175	231R	24		34-22-91	ALL
	G	18	2	W0175	229B	24		34-22-18	ALL
	G	18	2	W0175	230B	24		34-22-91	ALL
	G	18	2	W0175	231B	24		34-22-91	ALL
	G	19	2	W0165	229R	24		34-22-28	ALL
	G	19	2	W0165	230R	24		34-22-81	ALL
	G	19	2	W0165	231R	24		34-22-81	ALL
	G	2	2	W0165	025	24		34-33-11	ALL
	G	2	2	W0165	026	24		34-57-11	ALL
	G	2	2	W0165	027	24		34-57-11	ALL
	G	20	2	W0165	229B	24		34-22-28	ALL
	G	20	2	W0165	230B	24		34-22-81	ALL
	G	20	2	W0165	231B	24		34-22-81	ALL
	G	7	2	W0175	010	24		34-33-21	ALL
	G	7	2	W0175	011	24		34-33-21	ALL
	G	7	2	W0175	026	24		34-57-21	ALL
	G	9	2	W0165	031	24		34-57-11	ALL
	G	9	2	W0165	032	24		34-57-11	ALL
	G	9	2	W0165	033	24		34-57-11	ALL
	F	A001	2	W0165	010	24		34-33-21	ALL
	F	A001	2	W0175	007	24		34-33-21	ALL
	F	A008	2	W0165	227R	24		23-51-13	ALL
	F	A008	2	W0175	208R	24		23-51-13	ALL
	Y	A011	BJ	W0175	209R	24		31-35-13	ALL
	Y	A011	BJ	W0175	210R	24		34-57-21	ALL
	Y	A011	BJ	W0175	221R	24		34-57-21	ALL
	Y	A012	BJ	W0165	209R	24		31-35-13	ALL
	Y	A012	BJ	W0165	210R	24		34-57-11	ALL
	Y	A012	BJ	W0165	221R	24		34-57-11	ALL
	F	C001	2	W0165	015	24		34-33-31	ALL
	F	C001	2	W0185	007	24		34-33-31	ALL
	F	C008	2	W0165	227B	24		23-51-13	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 270

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0165		284T0151 (continued)					SHELF/E05/01		ALL
TB0165	F	BACM15C1A (continued)					SHELF/E05/01		ALL
TB0165	G	BACM15C1B (continued)					SHELF/E05/01		ALL
TB0165	X	BACM15C3A (continued)					SHELF/E05/01		ALL
TB0165	Y	BACM15C3B (continued)					SHELF/E05/01		ALL
TB0165	Z	BACM15C3B (continued)					SHELF/E05/01		ALL
	F	C008	2	W0175	208B	24		23-51-13	ALL
	Y	C011	BJ	W0175	209B	24		31-35-13	ALL
	Y	C011	BJ	W0175	210B	24		34-57-21	ALL
	Y	C011	BJ	W0175	221B	24		34-57-21	ALL
	Y	C012	BJ	W0165	209B	24		31-35-13	ALL
	Y	C012	BJ	W0165	210B	24		34-57-11	ALL
	Y	C012	BJ	W0165	221B	24		34-57-11	ALL
	Y	REF		W0165	209	20		31-35-13	ALL
	Y	REF		W0165	209Z			31-35-13	ALL
	Y	REF		W0165	210	20		34-57-11	ALL
	Y	REF		W0165	210Z			34-57-11	ALL
	Y	REF		W0165	221	20		34-57-11	ALL
	Y	REF		W0165	221Z			34-57-11	ALL
	G	REF		W0165	229	20		34-22-28	ALL
	G	REF		W0165	229Z			34-22-28	ALL
	G	REF		W0165	230	20		34-22-81	ALL
	G	REF		W0165	230Z			34-22-81	ALL
	G	REF		W0165	231	20		34-22-81	ALL
	G	REF		W0165	231Z			34-22-81	ALL
	Y	REF		W0175	209	20		31-35-13	ALL
	Y	REF		W0175	209Z			31-35-13	ALL
	Y	REF		W0175	210	20		34-57-21	ALL
	Y	REF		W0175	210Z			34-57-21	ALL
	Y	REF		W0175	221	20		34-57-21	ALL
	Y	REF		W0175	221Z			34-57-21	ALL
	G	REF		W0175	229	20		34-22-18	ALL
	G	REF		W0175	229Z			34-22-18	ALL
	G	REF		W0175	230	20		34-22-91	ALL
	G	REF		W0175	230Z			34-22-91	ALL
	G	REF		W0175	231	20		34-22-91	ALL
	G	REF		W0175	231Z			34-22-91	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 271

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0166		284T0603					SHELF/E03/01		ALL
TB0166	D	DIODE-BLOCK-REF284T0131-					SHELF/E03/01		050-099, 151-199, 275-299
TB0166	F	BACM15C1A					SHELF/E03/01		ALL
TB0166	G	BACM15C1B					SHELF/E03/01		ALL
TB0166	X	BACM15C3A					SHELF/E03/01		ALL
TB0166	Y	BACM15C3B					SHELF/E03/01		050-099, 151-199, 275-299
	G	1	2	W0082	301Y	24		21-51-12	150
	G	1	2	W0082	305Y	24		21-51-12	ALL
	G	1	2	W0084	305Y	24		21-51-22	ALL
	G	11	2	W0082	227B	24		21-51-12	150
	G	11	2	W0082	228B	24		21-51-12	150
	G	11	2	W0084	233B	24		21-51-22	150
	G	12	2	W0082	227R	24		21-51-12	150
	G	12	2	W0082	228R	24		21-51-12	150
	G	12	2	W0084	233R	24		21-51-22	150
	G	2	2	W0082	301B	24		21-51-12	150
	G	2	2	W0082	305B	24		21-51-12	ALL
	G	2	2	W0084	305B	24		21-51-22	ALL
	G	3	2	W0082	301R	24		21-51-12	150
	G	3	2	W0082	305R	24		21-51-12	150
	G	3	2	W0084	305R	24		21-51-22	150
	D	A003	2	W0084	305R	24		21-51-22	050-099, 151-199, 275-299
	X	A004	BJ	W0082	217B	24		21-61-51	ALL
	X	A004	BJ	W0084	217B	24		21-61-51	ALL
	X	A005	BJ	W0082	148	24		21-61-31	ALL
	X	A005	BJ	W0084	143	24		21-61-31	ALL
	X	A006	BJ	W0082	144	24		21-61-11	ALL
	X	A006	BJ	W0084	139	24		21-61-11	ALL
	X	A007	BJ	W0082	146	24		21-61-21	ALL
	X	A007	BJ	W0084	141	24		21-61-21	ALL
	F	A008	2	W0082	100	24		21-61-31	ALL
	F	A008	2	W0084	033	24		21-61-31	ALL
	F	A009	2	W0082	131	24		36-23-11	ALL
	F	A009	2	W0084	068	24		36-23-11	ALL
	F	A010	2	W0082	219B	24		21-52-41	ALL
	F	A010	2	W0084	229B	24		21-52-41	ALL
	Y	A011	BJ	W0082	227B	24		21-51-12	050-099, 151-199, 275-299
	Y	A011	BJ	W0082	228B	24		21-51-12	050-099, 151-199, 275-299
	Y	A011	BJ	W0084	233B	24		21-51-22	050-099, 151-199, 275-299
	Y	A012	BJ	W0082	227R	24		21-51-12	050-099, 151-199, 275-299
	Y	A012	BJ	W0082	228R	24		21-51-12	050-099, 151-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 272

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0166		284T0603 (continued)					SHELF/E03/01		ALL
TB0166	D	DIODE-BLOCK-REF284T0131- (continued)					SHELF/E03/01		050-099, 151-199, 275-299
TB0166	F	BACM15C1A (continued)					SHELF/E03/01		ALL
TB0166	G	BACM15C1B (continued)					SHELF/E03/01		ALL
TB0166	X	BACM15C3A (continued)					SHELF/E03/01		ALL
TB0166	Y	BACM15C3B (continued)					SHELF/E03/01		050-099, 151-199, 275-299
	Y	A012	BJ	W0084	233R	24		21-51-22	050-099, 151-199, 275-299
	F	A013	2	W0082	220R	24		21-52-41	ALL
	F	A013	2	W0084	230R	24		21-52-41	ALL
	F	A014	2	W0082	224R	24		21-52-41	ALL
	F	A014	2	W0084	231R	24		21-52-41	ALL
	F	A015	2	W0082	401B	24		21-52-41	ALL
	F	A015	2	W0084	401B	24		21-52-41	ALL
	F	A016	2	W0082	401R	24		21-52-41	ALL
	F	A016	2	W0084	401R	24		21-52-41	ALL
	X	B004	BJ	W0082	217R	24		21-61-51	ALL
	X	B004	BJ	W0084	217R	24		21-61-51	ALL
	X	B005	BJ	W0082	149	24		21-61-31	ALL
	X	B005	BJ	W0084	144	24		21-61-31	ALL
	X	B006	BJ	W0082	145	24		21-61-11	ALL
	X	B006	BJ	W0084	140	24		21-61-11	ALL
	X	B007	BJ	W0082	147	24		21-61-21	ALL
	X	B007	BJ	W0084	142	24		21-61-21	ALL
	D	C003	2	W0082	305R	24		21-51-12	050-099, 151-199, 275-299
	D	C003	2	W0082	550	24		21-51-12	050-099, 151-199, 275-299
	X	C004	BJ	W0082	218B	24		21-61-51	ALL
	X	C004	BJ	W0084	218B	24		21-61-51	ALL
	X	C005	BJ	W0082	154	22		36-23-11	ALL
	X	C005	BJ	W0084	065	22		36-23-11	ALL
	X	C006	BJ	W0082	096	24		21-61-11	ALL
	X	C006	BJ	W0084	029	24		21-61-11	ALL
	X	C007	BJ	W0082	099	24		21-61-21	ALL
	X	C007	BJ	W0084	028	24		21-61-21	ALL
	F	C008	2	W0082	101	24		21-61-31	ALL
	F	C008	2	W0084	034	24		21-61-31	ALL
	F	C009	2	W0082	132	24		36-23-11	ALL
	F	C009	2	W0084	057	24		36-23-11	ALL
	F	C010	2	W0082	219R	24		21-52-41	ALL
	F	C010	2	W0084	229R	24		21-52-41	ALL
	Y	C011	BJ	W0082	204B	22		21-51-12	050-099, 151-199, 275-299
	Y	C011	BJ	W0082	232B	22		21-51-12	050-099, 151-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 273

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0166		<b>284T0603 (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0166	<b>D</b>	<b>DIODE-BLOCK-REF284T0131- (continued)</b>					<b>SHELF/E03/01</b>		<b>050-099, 151-199, 275-299</b>
TB0166	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0166	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0166	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0166	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>SHELF/E03/01</b>		<b>050-099, 151-199, 275-299</b>
	Y	C011	BJ	W0082	238B	22		21-51-12	050-099, 151-199, 275-299
	Y	C012	BJ	W0082	204R	22		21-51-12	050-099, 151-199, 275-299
	Y	C012	BJ	W0082	232R	22		21-51-12	050-099, 151-199, 275-299
	Y	C012	BJ	W0082	238R	22		21-51-12	050-099, 151-199, 275-299
	F	C013	2	W0082	224B	24		21-52-41	ALL
	F	C013	2	W0084	231B	24		21-52-41	ALL
	F	C014	2	W0082	220B	24		21-52-41	ALL
	F	C014	2	W0084	230B	24		21-52-41	ALL
	F	C015	2	W0082	401G	24		21-52-41	ALL
	F	C015	2	W0084	401G	24		21-52-41	ALL
	F	C016	2	W0082	401Y	24		21-52-41	ALL
	F	C016	2	W0084	401Y	24		21-52-41	ALL
	X	D004	BJ	W0082	218R	24		21-61-51	ALL
	X	D004	BJ	W0084	218R	24		21-61-51	ALL
	X	D005	BJ	W0082	153	22		36-23-11	ALL
	X	D005	BJ	W0084	064	22		36-23-11	ALL
	X	D006	BJ	W0082	097	24		21-61-11	ALL
	X	D006	BJ	W0084	030	24		21-61-11	ALL
	X	D007	BJ	W0082	098	24		21-61-21	ALL
	X	D007	BJ	W0084	027	24		21-61-21	ALL
	F	DED		W0082	219Z			21-52-41	ALL
	F	DED		W0082	220Z			21-52-41	ALL
	F	DED		W0082	224Z			21-52-41	ALL
	F	DED		W0082	401Z			21-52-41	ALL
<b>TB0168</b>		<b>284T0603</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
<b>TB0168</b>	<b>F</b>	<b>BACM15C1A</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
<b>TB0168</b>	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
<b>TB0168</b>	<b>X</b>	<b>BACM15C3A</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
	G	10	2	W0082	083	18		36-11-51	ALL
	G	10	2	W0084	059	24		36-23-11	ALL
	G	11	2	W0082	085	18		36-11-51	ALL
	G	11	2	W0084	055	24		36-23-11	ALL
	G	13	2	W0082	090	24		36-11-61	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 274

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0168		<b>284T0603 (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
	G	13	2	W0082	091	24		36-11-61	ALL
	G	13	2	W0084	056	24		36-23-11	ALL
	G	14	2	W0082	092	18		36-11-61	050-099, 150-156, 162-166, 275-276
	G	14	2	W0082	093	18		36-11-61	050-099, 150-156, 162-166, 275-276
	G	15	2	W0082	095	24		36-11-61	ALL
	G	15	2	W0084	067	24		36-23-11	ALL
	X	A001	BJ	W0082	070	24		36-23-11	050-099, 156-162, 166-199, 277-299
	F	A001	2	W0082	070	24		36-23-11	150-155, 163-165, 275-276
	X	A001	BJ	W0084	049	24		36-23-11	ALL
	F	A002	2	W0082	072	24		36-23-11	150-155, 163-165, 275-276
	X	A002	BJ	W0082	312B	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	A002	BJ	W0084	314B	24		36-23-11	ALL
	X	A003	BJ	W0082	075	24		36-23-11	050-099, 156-162, 166-199, 277-299
	F	A003	2	W0082	312B	24		36-23-11	150-155, 163-165, 275-276
	X	A003	BJ	W0084	053	24		36-23-11	ALL
	X	A004	BJ	W0082	239R	24		36-23-11	050-099, 156-162, 166-199, 277-299
	F	A004	2	W0082	312Y	24		36-23-11	150-155, 163-165, 275-276
	X	A004	BJ	W0084	269R	24		36-23-11	ALL
	F	A005	2	W0082	075	24		36-23-11	150-155, 163-165, 275-276
	X	A005	BJ	W0082	166	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	A005	BJ	W0084	157	24		36-23-11	ALL
	F	A006	2	W0082	077	24		36-23-11	150-155, 163-165, 275-276
	X	A006	BJ	W0082	161	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	A006	BJ	W0084	150	24		36-23-11	ALL
	F	A007	2	W0082	079	24		36-23-11	ALL
	F	A007	2	W0084	062	24		36-23-11	ALL
	F	A008	2	W0082	082	24		36-23-11	ALL
	F	A008	2	W0084	058	24		36-23-11	ALL
	F	A009	2	W0082	081	24		36-23-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 275

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0168		<b>284T0603 (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
	F	A009	2	W0084	066	24		36-23-11	ALL
	F	A016	2	W0082	313Y	24		21-61-41	050-099
	X	A016	BJ	W0082	313Y	24		21-61-41	150-199, 275-299
	F	A016	2	W0084	317Y	24		21-61-41	050-099
	X	A016	BJ	W0084	317Y	24		21-61-41	150-199, 275-299
	X	A017	BJ	W0082	135	24		21-51-11	150-199, 275-299
	F	A017	2	W0082	313B	24		21-61-41	050-099
	X	A017	BJ	W0084	128	24		21-51-11	150-199, 275-299
	F	A017	2	W0084	317B	24		21-61-41	050-099
	X	B001	BJ	W0082	072	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	B001	BJ	W0084	051	24		36-23-11	ALL
	X	B002	BJ	W0082	312Y	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	B002	BJ	W0084	314Y	24		36-23-11	ALL
	X	B003	BJ	W0082	077	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	B003	BJ	W0084	060	24		36-23-11	ALL
	X	B004	BJ	W0082	239B	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	B004	BJ	W0084	269B	24		36-23-11	ALL
	X	B005	BJ	W0082	167	22		36-23-11	050-099, 157-162, 167-199, 277-299
	X	B005	BJ	W0082	167	24		36-23-11	156, 166
	X	B005	BJ	W0084	159	22		36-23-11	ALL
	X	B016	BJ	W0082	313R	24		21-61-41	150-199, 275-299
	X	B016	BJ	W0084	317R	24		21-61-41	150-199, 275-299
	X	B017	BJ	W0082	136	24		21-51-11	150-199, 275-299
	X	B017	BJ	W0084	129	24		21-51-11	150-199, 275-299
	X	C001	BJ	W0082	071	24		36-23-11	050-099, 156-162, 166-199, 277-299
	F	C001	2	W0082	071	24		36-23-11	150-155, 163-165, 275-276
	X	C001	BJ	W0084	050	24		36-23-11	ALL
	F	C002	2	W0082	074	24		36-23-11	150-155, 163-165, 275-276
	X	C002	BJ	W0082	312R	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	C002	BJ	W0084	314R	24		36-23-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 276

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0168		<b>284T0603 (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	F	<b>BACM15C1A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	G	<b>BACM15C1B (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
TB0168	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E03/01</b>		<b>ALL</b>
	X	C003	BJ	W0082	076	24		36-23-11	050-099, 156-162, 166-199, 277-299
	F	C003	2	W0082	312R	24		36-23-11	150-155, 163-165, 275-276
	X	C003	BJ	W0084	054	24		36-23-11	ALL
	X	C004	BJ	W0082	164	24		36-23-11	050-099, 156-162, 166-199, 277-299
	F	C004	2	W0082	312Z			36-23-11	150-155, 163-165, 275-276
	X	C004	BJ	W0084	155	24		36-23-11	ALL
	F	C005	2	W0082	076	24		36-23-11	150-155, 163-165, 275-276
	X	C005	BJ	W0082	168	22		36-23-11	050-099, 156-162, 166-199, 277-299
	X	C005	BJ	W0084	160	22		36-23-11	ALL
	F	C006	2	W0082	078	24		36-23-11	150-155, 163-165, 275-276
	F	C007	2	W0082	080	24		36-23-11	ALL
	F	C007	2	W0084	063	24		36-23-11	ALL
	F	C009	2	W0082	102	24		36-23-11	ALL
	F	C009	2	W0084	069	18		36-23-11	ALL
	X	C016	BJ	W0082	313B	24		21-61-41	150-199, 275-299
	F	C016	2	W0082	313R	24		21-61-41	050-099
	X	C016	BJ	W0084	317B	24		21-61-41	150-199, 275-299
	F	C016	2	W0084	317R	24		21-61-41	050-099
	X	D001	BJ	W0082	074	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	D001	BJ	W0084	052	24		36-23-11	ALL
	X	D002	BJ	W0082	312Z			36-23-11	050-099, 156-162, 166-199, 277-299
	X	D002	BJ	W0084	314Z			36-23-11	ALL
	X	D003	BJ	W0082	078	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	D003	BJ	W0084	061	24		36-23-11	ALL
	X	D004	BJ	W0082	165	24		36-23-11	050-099, 156-162, 166-199, 277-299
	X	D004	BJ	W0084	156	24		36-23-11	ALL
	X	D005	BJ	W0082	169	22		36-23-11	050-099, 156-162, 166-199, 277-299
	X	D005	BJ	W0084	161	22		36-23-11	ALL
	F	DED		W0082	102Z			36-23-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 277

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0168		284T0603 (continued)					SHELF/E03/01		ALL
TB0168	F	BACM15C1A (continued)					SHELF/E03/01		ALL
TB0168	G	BACM15C1B (continued)					SHELF/E03/01		ALL
TB0168	X	BACM15C3A (continued)					SHELF/E03/01		ALL
	F	DED		W0084	069Z			36-23-11	ALL
TB0169	G	BACM15C1B					SHELF/E05/03		ALL
TB0170		284T0603					SHELF/E03/01		ALL
TB0170	F	BACM15C1A					SHELF/E03/01		ALL
TB0170	G	BACM15C1B					SHELF/E03/01		ALL
	G	13	2	W0084	043	24		36-11-62	ALL
	G	13	2	W0084	044	24		36-11-62	ALL
	G	13	2	W0084	084	24		36-23-21	ALL
	F	A008	2	W0082	127	24		21-51-21	150-199, 275-299
	F	A008	2	W0084	131	24		21-51-21	150-199, 275-299
	F	C007	2	W0082	126	24		21-51-21	150-199, 275-299
	F	C007	2	W0084	130	24		21-51-21	150-199, 275-299
TB0174		BACT44B1350U					P019-00/ /		050-099
TB0174		BACT44B1550U					P019-00/ /		150-199, 275-299
TB0174	D	YHLZD-30					P019-00/ /		050-099, 150-199
TB0174	F	BACM15C1A					P019-00/ /		ALL
TB0174	G	BACM15C1B					P019-00/ /		ALL
TB0174	H	BACM15C2A					P019-00/ /		ALL
TB0174	X	BACM15C3A					P019-00/ /		ALL
TB0174	Y	BACM15C3B					P019-00/ /		ALL
TB0174	Z	BACM15C37					P019-00/ /		ALL
	Z	10	BJ	W1104	070	20		33-21-31	050-099, 150-199
	Z	10	BJ	W1104	074	20		33-21-31	150-157
	Z	10	BJ	W1104	077	20		33-21-31	050-099, 150-199
	Z	10	BJ	W1104	080	20		33-21-31	150-199
	Z	10	BJ	W1104	089	20		33-21-31	050-099, 150-199
	G	22	2	W1060	516	24		23-31-13	ALL
	G	22	2	W1110	061	24		23-31-13	ALL
	G	22	2	W1110	063	24		23-31-13	ALL
	Z	23	BJ	W1058	206R	22		23-31-14	ALL
	Z	23	BJ	W1060	212R	22		23-31-14	275-299
	Z	23	BJ	W1060	213R	22		23-31-14	ALL
	Z	23	BJ	W1060	214R	22		23-31-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 278

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0174		BACT44B1350U (continued)					P019-00/ /		050-099
TB0174		BACT44B1550U (continued)					P019-00/ /		150-199, 275-299
TB0174	D	YHLZD-30 (continued)					P019-00/ /		050-099, 150-199
TB0174	F	BACM15C1A (continued)					P019-00/ /		ALL
TB0174	G	BACM15C1B (continued)					P019-00/ /		ALL
TB0174	H	BACM15C2A (continued)					P019-00/ /		ALL
TB0174	X	BACM15C3A (continued)					P019-00/ /		ALL
TB0174	Y	BACM15C3B (continued)					P019-00/ /		ALL
TB0174	Z	BACM15C37 (continued)					P019-00/ /		ALL
	Z	23	BJ	W1060	215R	22		23-31-14	ALL
	Z	23	BJ	W1060	216R	22		23-31-14	ALL
	Z	23	BJ	W1060	217R	22		23-31-14	ALL
	Z	23	BJ	W1102	201R	22		23-31-14	ALL
	Z	24	BJ	W1058	206B	22		23-31-14	ALL
	Z	24	BJ	W1060	212B	22		23-31-14	275-299
	Z	24	BJ	W1060	213B	22		23-31-14	ALL
	Z	24	BJ	W1060	214B	22		23-31-14	ALL
	Z	24	BJ	W1060	215B	22		23-31-14	ALL
	Z	24	BJ	W1060	216B	22		23-31-14	ALL
	Z	24	BJ	W1060	217B	22		23-31-14	ALL
	Z	24	BJ	W1102	201B	22		23-31-14	ALL
	Z	27	BJ	W1060	692	22		30-46-11	ALL
	Z	27	BJ	W1060	693	22		30-46-11	ALL
	Z	27	BJ	W1060	694	22		30-46-11	ALL
	Z	27	BJ	W1060	695	22		30-46-11	ALL
	Z	28	BJ	W1060	526	20		33-21-11	050-099
	Z	28	BJ	W1060	532	20		33-21-31	050-099
	Z	28	BJ	W1060	687	20		33-21-31	155-157, 166-199
	Z	28	BJ	W1060	731	24		33-21-31	050-099, 150-199
	Z	28	BJ	W1060	737	24		33-21-11	150-199
	Z	28	BJ	W1060	773	24		33-21-31	050-099, 150-199
	Z	28	BJ	W1060	778	24		33-21-12	050-099, 150-199
	Z	28	BJ	W1060	804	24		33-21-31	050-099, 155-199
	Z	28	BJ	W1060	804	20		33-21-31	150-154
	Z	28	BJ	W1104	729	24		33-21-11	050-099, 150-199
	Z	28	BJ	W1104	731	24		33-21-11	050-099, 150-199
	Z	28	BJ	W1104	832	20		33-21-31	150-154, 162-165
	Z	29	BJ	W1060	100	20		33-27-11	ALL
	Z	29	BJ	W1060	101	22		33-27-11	ALL
	Z	29	BJ	W1104	125	22		33-27-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 279

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0174		BACT44B1350U (continued)					P019-00/ /		050-099
TB0174		BACT44B1550U (continued)					P019-00/ /		150-199, 275-299
TB0174	D	YHLZD-30 (continued)					P019-00/ /		050-099, 150-199
TB0174	F	BACM15C1A (continued)					P019-00/ /		ALL
TB0174	G	BACM15C1B (continued)					P019-00/ /		ALL
TB0174	H	BACM15C2A (continued)					P019-00/ /		ALL
TB0174	X	BACM15C3A (continued)					P019-00/ /		ALL
TB0174	Y	BACM15C3B (continued)					P019-00/ /		ALL
TB0174	Z	BACM15C37 (continued)					P019-00/ /		ALL
	Z	29	BJ	W1104	126	22		33-27-11	ALL
	Z	29	BJ	W1104	133	20		33-27-11	162-199
	Z	29	BJ	W1104	136	20		33-27-11	162-199
	H	3	2	W1058	004	18		26-13-11	050-099
	G	3	2	W1058	004	18		26-13-11	150-157
	H	3	2	W1058	601	18		26-13-11	050-099
	G	3	2	W1058	601	18		26-13-11	150-157
	G	3	2	W1104	505	16		33-21-31	162-199
	G	3	2	W1104	575	16		33-21-31	162-199
	H	3	2	W1104	591	18		26-13-11	050-099
	G	3	2	W1104	591	18		26-13-11	150-157
	G	31	2	W1104	116	16		38-13-11	275-299
	G	31	2	W1104	118	16		38-13-11	275-299
	G	31	2	W1104	501	16		38-13-11	275-299
	Z	33	BJ	W1060	220R	22		23-31-14	050-099, 150-199
	Z	33	BJ	W1060	221R	22		23-31-14	050-099, 150-199
	Z	33	BJ	W1060	222R	22		23-31-14	050-099, 150-199
	Z	33	BJ	W1060	223R	22		23-31-14	050-099, 150-199
	Z	33	BJ	W1102	202R	22		23-31-14	050-099, 150-199
	Z	34	BJ	W1060	220B	22		23-31-14	050-099, 150-199
	Z	34	BJ	W1060	221B	22		23-31-14	050-099, 150-199
	Z	34	BJ	W1060	222B	22		23-31-14	050-099, 150-199
	Z	34	BJ	W1060	223B	22		23-31-14	050-099, 150-199
	Z	34	BJ	W1102	202B	22		23-31-14	050-099, 150-199
	Z	36	BJ	W1058	009	22		33-26-11	150-199
	Z	36	BJ	W1058	010	22		33-26-11	150-199
	Z	36	BJ	W1058	022	22		33-24-11	050-099
	Z	36	BJ	W1060	068	22		33-24-11	050-099
	Z	36	BJ	W1060	782	22		33-24-11	050-099
	Z	36	BJ	W1060	788	20		33-24-11	050-099
	Z	36	BJ	W1102	011	22		33-26-11	150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 280

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0174		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0174		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0174	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P019-00/ /</b>		<b>050-099, 150-199</b>
TB0174	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Z</b>	<b>BACM15C37 (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Z	36	BJ	W1102	023	22		33-26-11	150-199
	Z	36	BJ	W1104	114	22		33-26-11	150-199
	Z	36	BJ	W1104	769	20		33-24-11	050-099
	Z	37	BJ	W1060	022	20		33-24-11	275-299
	Z	37	BJ	W1060	068	20		33-24-11	275-299
	Z	37	BJ	W1060	600	20		33-22-11	050-099, 150-199
	Z	37	BJ	W1060	600	20		33-24-11	275-299
	Z	37	BJ	W1060	699	20		33-22-31	050-099, 150-199
	Z	37	BJ	W1060	710	20		33-22-32	050-099, 150-199
	Z	37	BJ	W1060	711	20		33-22-11	050-099, 150-199
	Z	37	BJ	W1104	599	24		33-21-31	050-099, 150-199
	Z	37	BJ	W1104	664	24		33-21-31	050-099, 150-199
	Z	37	BJ	W1104	665	24		33-21-11	050-099, 150-199
	Z	37	BJ	W1104	769	20		33-24-11	275-299
	Z	37	BJ	W1110	077	20		33-24-11	275-299
	Z	38	BJ	W1058	500	22		33-24-11	050-099
	Z	38	BJ	W1058	500	20		33-24-11	275-299
	Z	38	BJ	W1060	021	20		33-24-11	275-299
	Z	38	BJ	W1060	072	20		33-24-11	275-299
	Z	38	BJ	W1060	711	20		33-24-11	275-299
	Z	38	BJ	W1060	713	22		33-24-11	050-099
	Z	38	BJ	W1060	714	22		33-24-11	050-099
	Z	38	BJ	W1060	714	20		33-24-11	275-299
	Z	38	BJ	W1060	787	20		33-24-11	050-099
	Z	38	BJ	W1104	655	20		33-24-11	275-299
	Z	38	BJ	W1104	770	20		33-24-11	050-099
	H	39	2	W1058	076	18		26-13-11	162-199
	H	39	2	W1058	077	18		26-13-11	162-199
	H	39	2	W1104	706	18		26-13-11	162-199
	G	4	2	W1104	014	16		33-21-31	150-199, 275-299
	G	4	2	W1104	090	16		33-21-31	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 281

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0174		BACT44B1350U (continued)					P019-00/ /		050-099
TB0174		BACT44B1550U (continued)					P019-00/ /		150-199, 275-299
TB0174	D	YHLZD-30 (continued)					P019-00/ /		050-099, 150-199
TB0174	F	BACM15C1A (continued)					P019-00/ /		ALL
TB0174	G	BACM15C1B (continued)					P019-00/ /		ALL
TB0174	H	BACM15C2A (continued)					P019-00/ /		ALL
TB0174	X	BACM15C3A (continued)					P019-00/ /		ALL
TB0174	Y	BACM15C3B (continued)					P019-00/ /		ALL
TB0174	Z	BACM15C37 (continued)					P019-00/ /		ALL
	G	4	2	W1104	526	16		33-21-31	150-199, 275-299
	G	4	2	W1104	551	16		33-21-31	150-199, 275-299
	G	4	2	W1104	575	16		33-21-31	280-299
	Z	41	BJ	W1058	070	20		26-13-11	050-099
	Z	41	BJ	W1060	828	20		26-13-12	050-099
	Z	41	BJ	W1060	880	20		26-13-12	050-099
	Z	41	BJ	W1102	083	20		26-13-11	050-099
	Z	41	BJ	W1104	799	20		26-13-11	050-099
	Z	42	BJ	W1058	068	20		26-13-11	050-099
	Z	42	BJ	W1060	826	20		26-13-12	050-099
	Z	42	BJ	W1060	829	20		26-13-12	050-099
	Z	42	BJ	W1102	081	20		26-13-11	050-099
	Z	42	BJ	W1104	797	20		26-13-11	050-099
	Z	43	BJ	W1058	069	20		26-13-11	050-099
	Z	43	BJ	W1060	824	20		26-13-12	050-099
	Z	43	BJ	W1060	827	20		26-13-12	050-099
	Z	43	BJ	W1102	082	20		26-13-11	050-099
	Z	43	BJ	W1104	798	20		26-13-11	050-099
	Z	9	BJ	W1060	036	22		33-22-11	050-099
	Z	9	BJ	W1060	036	20		33-22-11	150-199, 275-299
	Z	9	BJ	W1104	095	20		33-21-31	050-099
	Z	9	BJ	W1104	098	20		33-21-31	ALL
	Z	9	BJ	W1104	586	20		33-21-31	150-199, 275-299
	Z	9	BJ	W1104	587	20		33-21-31	ALL
	Z	9	BJ	W1104	605	20		33-21-31	ALL
	Z	9	BJ	W1104	806	20		33-21-31	050-099, 150-154, 157-165, 167-199
	Z	9	BJ	W1104	809	20		33-21-31	155-156
	Z	9	BJ	W1104	851	20		33-21-31	166
	X	A001	BJ	W1060	034	22		33-22-11	050-099
	X	A001	BJ	W1060	034	20		33-22-11	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 282

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0174		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0174		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0174	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P019-00/ /</b>		<b>050-099, 150-199</b>
TB0174	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Z</b>	<b>BACM15C37 (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	X	A001	BJ	W1104	117	22		33-22-11	050-099
	X	A001	BJ	W1104	117	20		33-22-11	150-199, 275-299
	X	A002	BJ	W1060	029	24		33-21-31	150-157, 275-299
	X	A002	BJ	W1104	064	24		33-21-31	150-157, 275-299
	Y	A005	BJ	W1060	751	24		33-21-31	050-099, 150-199
	Y	A005	BJ	W1104	081	24		33-21-12	050-099, 150-199
	Y	A005	BJ	W1104	083	24		33-21-12	050-099, 150-199
	Y	A006	BJ	W1060	028	24		33-21-31	ALL
	Y	A006	BJ	W1104	063	24		33-21-31	ALL
	Y	A006	BJ	W1104	100	24		33-21-31	ALL
	Y	A006	BJ	W1104	576	24		33-21-31	ALL
	F	A008	2	W1058	025	22		52-51-11	ALL
	F	A008	2	W1060	542	22		52-51-11	ALL
	Y	A011	BJ	W1060	809	24		33-21-12	050-099, 150-199
	Y	A011	BJ	W1104	776	24		33-21-12	050-099, 150-199
	Y	A012	BJ	W1104	068	20		33-21-31	050-099, 150-199
	Y	A012	BJ	W1104	086	20		33-21-31	050-099, 150-199
	Y	A012	BJ	W1104	087	20		33-21-31	150-199
	Y	A012	BJ	W1104	802	20		33-21-31	050-099
	Y	A013	BJ	W1060	012	22		33-21-21	050-099, 150-199
	Y	A013	BJ	W1060	026	22		33-21-21	150-199
	Y	A013	BJ	W1060	591	20		33-24-11	275-299
	Y	A013	BJ	W1060	679	22		33-21-21	050-099, 150-199
	Y	A013	BJ	W1060	708	22		33-21-21	050-099, 150-199
	Y	A013	BJ	W1060	710	20		33-24-11	275-299
	Y	A013	BJ	W1060	812	20		33-24-11	275-299
	Y	A013	BJ	W1104	561	20		33-24-11	275-299
	Y	A014	BJ	W1060	732	24		33-21-31	155-157, 166-199
	Y	A014	BJ	W1060	761	24		33-21-31	050-099, 150-154, 162-165
	Y	A014	BJ	W1060	777	24		33-21-12	050-099, 150-199
	Y	A014	BJ	W1104	771	24		33-21-12	050-099, 150-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 283

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0174		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0174		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0174	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P019-00/ /</b>		<b>050-099, 150-199</b>
TB0174	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Z</b>	<b>BACM15C37 (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Y	A015	BJ	W1060	195	22		52-11-12	050-099, 150-199
	Y	A015	BJ	W1060	195	20		52-11-12	275-299
	Y	A015	BJ	W1060	196	24		52-11-12	ALL
	Y	A015	BJ	W1060	198	22		52-11-12	ALL
	Y	A016	BJ	W1060	180	22		52-11-12	ALL
	Y	A016	BJ	W1060	181	22		52-11-12	ALL
	Y	A016	BJ	W1060	182	22		52-11-12	ALL
	Y	A016	BJ	W1060	190	22		52-11-12	ALL
	Y	A017	BJ	W1060	176	22		52-11-12	ALL
	Y	A017	BJ	W1060	191	22		52-11-12	ALL
	Y	A017	BJ	W1060	197	22		52-11-12	ALL
	Y	A018	BJ	W1104	082	20		33-21-31	150-199
	Y	A018	BJ	W1104	092	20		33-21-31	150-199
	Y	A018	BJ	W1104	103	20		33-21-31	150-199
	X	A019	BJ	W1060	625	22		33-21-21	ALL
	X	A019	BJ	W1110	081	22		33-21-21	ALL
	D	A021	2	W1058	042	22		33-25-11	050-099, 150-199
	D	A021	2	W1102	106	22		33-25-11	050-099, 150-199
	Y	A025	BJ	W1060	216R	22		23-31-14	275-299
	Y	A025	BJ	W1060	236R	22		23-31-14	275-299
	Y	A025	BJ	W1104	202R	22		23-31-14	275-299
	X	A031	BJ	W1058	073	20		26-13-12	050-099
	X	A031	BJ	W1060	830	20		26-13-12	050-099
	X	A032	BJ	W1058	064	20		26-13-12	050-099
	X	A032	BJ	W1060	825	20		26-13-12	050-099
	Y	A042	BJ	W1058	078	20		26-13-12	162-199
	Y	A042	BJ	W1060	067	20		26-13-12	162-199
	Y	A042	BJ	W1060	844	20		26-13-12	162-199
	Y	A043	BJ	W1058	080	20		26-13-12	162-199
	Y	A043	BJ	W1060	843	20		26-13-12	162-199
	Y	A043	BJ	W1060	846	20		26-13-12	162-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 284

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0174		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0174		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0174	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P019-00/ /</b>		<b>050-099, 150-199</b>
TB0174	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Z</b>	<b>BACM15C37 (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	X	B001	BJ	W1060	009	22		33-21-21	ALL
	X	B001	BJ	W1104	600	22		33-21-21	ALL
	X	B019	BJ	W1060	633	22		33-22-42	ALL
	X	B019	BJ	W1110	083	22		33-22-42	ALL
	X	B020	BJ	W1060	739	24		33-21-31	050-099
	X	B020	BJ	W1060	739	20		33-21-31	150-199
	X	B020	BJ	W1104	723	24		33-21-31	050-099, 150-199
	X	B031	BJ	W1058	066	20		26-13-11	050-099
	X	B031	BJ	W1104	795	20		26-13-11	050-099
	X	C001	BJ	W1058	016	20		26-13-11	050-099, 150-199
	X	C001	BJ	W1104	601	20		26-13-11	050-099, 150-199
	X	C002	BJ	W1060	053	22		33-22-41	ALL
	X	C002	BJ	W1104	145	22		33-22-41	ALL
	Y	C005	BJ	W1060	740	24		33-21-31	050-099
	Y	C005	BJ	W1104	603	20		33-21-31	150-199, 275-299
	Y	C005	BJ	W1104	609	20		33-21-31	150-199, 275-299
	Y	C005	BJ	W1104	610	20		33-21-31	150-199, 275-299
	Y	C005	BJ	W1104	611	20		33-21-31	275-299
	Y	C005	BJ	W1104	724	24		33-21-31	050-099
	Y	C005	BJ	W1104	800	24		33-21-31	050-099
	Y	C006	BJ	W1060	030	24		33-21-31	ALL
	Y	C006	BJ	W1104	101	24		33-21-31	275-278
	Y	C006	BJ	W1104	588	24		33-21-12	050-099, 150-199
	Y	C006	BJ	W1104	588	24		33-21-31	275-299
	Y	C006	BJ	W1104	645	24		33-21-12	050-099, 150-199
	F	C008	2	W1058	026	22		52-51-11	ALL
	F	C008	2	W1060	538	22		52-51-11	ALL
	Y	C011	BJ	W1060	807	24		33-21-12	050-099, 150-199
	Y	C011	BJ	W1104	066	24		33-21-12	155-157, 166-199
	Y	C011	BJ	W1104	777	24		33-21-12	050-099, 150-154, 162-165
	Y	C012	BJ	W1060	029	24		33-21-31	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 285

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0174		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0174		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0174	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P019-00/ /</b>		<b>050-099, 150-199</b>
TB0174	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Z</b>	<b>BACM15C37 (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Y	C012	BJ	W1060	831	24		33-21-31	050-099
	Y	C012	BJ	W1104	064	24		33-21-31	050-099
	Y	C012	BJ	W1104	123	20		33-21-31	150-199, 275-299
	Y	C012	BJ	W1104	124	20		33-21-31	150-199, 275-299
	Y	C012	BJ	W1104	525	20		33-21-31	150-199, 275-299
	Y	C012	BJ	W1104	608	20		33-21-31	162-199
	Y	C013	BJ	W1060	029	24		33-21-31	162-199
	Y	C013	BJ	W1060	831	24		33-21-31	162-199
	Y	C013	BJ	W1104	064	24		33-21-31	162-199
	Y	C015	BJ	W1060	186	22		52-11-12	ALL
	Y	C015	BJ	W1060	187	22		52-11-12	ALL
	Y	C015	BJ	W1060	189	22		52-11-12	ALL
	Y	C016	BJ	W1060	178	22		52-11-12	ALL
	Y	C016	BJ	W1060	179	22		52-11-12	ALL
	Y	C016	BJ	W1060	188	22		52-11-12	ALL
	X	C019	BJ	W1060	111	20		33-51-11	ALL
	X	C019	BJ	W1110	092	20		33-51-11	ALL
	X	C020	BJ	W1060	740	20		33-21-31	150, 153-154
	D	C021	2	W1058	040	22		33-25-11	050-099, 150-199
	D	C021	2	W1102	107	22		33-25-11	050-099, 150-199
	Y	C025	BJ	W1060	216B	22		23-31-14	275-299
	Y	C025	BJ	W1060	236B	22		23-31-14	275-299
	Y	C025	BJ	W1060	806	24		33-21-12	050-099, 150-199
	Y	C025	BJ	W1104	202B	22		23-31-14	275-299
	Y	C025	BJ	W1104	778	24		33-21-12	050-099, 150-199
	Y	C026	BJ	W1058	082	20		26-13-12	050-099
	Y	C026	BJ	W1060	842	20		26-13-12	050-099
	Y	C026	BJ	W1060	848	20		26-13-12	050-099
	X	C031	BJ	W1058	067	20		26-13-11	050-099
	X	C031	BJ	W1104	796	20		26-13-11	050-099
	Y	C042	BJ	W1058	079	20		26-13-12	162-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 286

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0174		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0174		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0174	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P019-00/ /</b>		<b>050-099, 150-199</b>
TB0174	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Z</b>	<b>BACM15C37 (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	Y	C042	BJ	W1060	845	20		26-13-12	162-199
	Y	C042	BJ	W1060	880	20		26-13-12	162-199
	Y	C043	BJ	W1058	082	20		26-13-12	162-199
	Y	C043	BJ	W1060	842	20		26-13-12	162-199
	Y	C043	BJ	W1060	848	20		26-13-12	162-199
	X	D001	BJ	W1060	709	24		33-21-31	050-099, 150-199, 280-299
	X	D001	BJ	W1104	101	24		33-21-31	280-299
	X	D001	BJ	W1104	500	24		33-21-31	050-099, 150-199
	X	D019	BJ	W1060	114	20		33-51-11	ALL
	X	D019	BJ	W1110	089	20		33-51-11	ALL
	X	D020	BJ	W1060	741	24		33-21-31	050-099, 162-199
	X	D020	BJ	W1060	741	20		33-21-31	150-157
	X	D020	BJ	W1104	725	24		33-21-31	050-099, 150-199
	X	D031	BJ	W1058	071	20		26-13-11	050-099
	X	D031	BJ	W1102	084	20		26-13-11	050-099
	Z	DED		W1058	500Z			33-24-11	277-299
	X	DED		W1060	034Z			33-22-11	155-156, 166
	Z	DED		W1060	036Z			33-22-11	155-156, 166
	G	DED		W1104	014Z			33-21-31	155-156, 166
	Z	DED		W1104	074Z			33-21-31	155-156
	Z	DED		W1104	077Z			33-21-31	155-156, 166
	Z	DED		W1104	080Z			33-21-31	155-156, 166
	Y	DED		W1104	082Z			33-21-31	155-156, 166
	Y	DED		W1104	086Z			33-21-31	155-156, 166
	Y	DED		W1104	087Z			33-21-31	155-156, 166
	Z	DED		W1104	089Z			33-21-31	155-156, 166
	Y	DED		W1104	103Z			33-21-31	155-156, 166
	X	DED		W1104	117Z			33-22-11	155-156, 166
	Y	DED		W1104	123Z			33-21-31	155-156, 166
	Y	DED		W1104	124Z			33-21-31	155-156, 166
	G	DED		W1104	505Z			33-21-31	166

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 287

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0174		<b>BACT44B1350U (continued)</b>					<b>P019-00/ /</b>		<b>050-099</b>
TB0174		<b>BACT44B1550U (continued)</b>					<b>P019-00/ /</b>		<b>150-199, 275-299</b>
TB0174	<b>D</b>	<b>YHLZD-30 (continued)</b>					<b>P019-00/ /</b>		<b>050-099, 150-199</b>
TB0174	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
TB0174	<b>Z</b>	<b>BACM15C37 (continued)</b>					<b>P019-00/ /</b>		<b>ALL</b>
	<b>G</b>	<b>DED</b>		<b>W1104</b>	<b>526Z</b>			<b>33-21-31</b>	<b>155-156, 166</b>
	<b>G</b>	<b>DED</b>		<b>W1104</b>	<b>551Z</b>			<b>33-21-31</b>	<b>155-156, 166</b>
	<b>Z</b>	<b>DED</b>		<b>W1104</b>	<b>586Z</b>			<b>33-21-31</b>	<b>166</b>
	<b>Y</b>	<b>DED</b>		<b>W1104</b>	<b>608Z</b>			<b>33-21-31</b>	<b>166</b>
	<b>Z</b>	<b>DED</b>		<b>W1110</b>	<b>077Z</b>			<b>33-24-11</b>	<b>277-278</b>
	<b>X</b>	<b>DED</b>		<b>W1110</b>	<b>089Z</b>			<b>33-51-11</b>	<b>ALL</b>
	<b>X</b>	<b>DED</b>		<b>W1110</b>	<b>092Z</b>			<b>33-51-11</b>	<b>ALL</b>
<b>TB0176</b>		<b>284T0384</b>					<b>SHELF/E02/04</b>		<b>ALL</b>
<b>TB0176</b>	<b>D</b>	<b>DIODEBLOCK-REF284T0124-</b>					<b>SHELF/E02/04</b>		<b>ALL</b>
<b>TB0176</b>	<b>F</b>	<b>BACM15C1A</b>					<b>SHELF/E02/04</b>		<b>ALL</b>
<b>TB0176</b>	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E02/04</b>		<b>ALL</b>
<b>TB0176</b>	<b>R</b>	<b>RESISTORBLOCK-REF284T0124-</b>					<b>SHELF/E02/04</b>		<b>ALL</b>
<b>TB0176</b>	<b>X</b>	<b>BACM15C3A</b>					<b>SHELF/E02/04</b>		<b>ALL</b>
<b>TB0176</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>SHELF/E02/04</b>		<b>275-299</b>
	<b>G</b>	<b>1</b>	<b>2</b>	<b>W0016</b>	<b>166</b>	<b>24</b>		<b>24-51-71</b>	<b>ALL</b>
	<b>G</b>	<b>1</b>	<b>2</b>	<b>W0018</b>	<b>032</b>	<b>24</b>		<b>24-51-71</b>	<b>ALL</b>
	<b>G</b>	<b>1</b>	<b>2</b>	<b>W0018</b>	<b>033</b>	<b>24</b>		<b>24-51-71</b>	<b>ALL</b>
	<b>G</b>	<b>10</b>	<b>2</b>	<b>W0014</b>	<b>031</b>	<b>24</b>		<b>27-51-41</b>	<b>ALL</b>
	<b>G</b>	<b>10</b>	<b>2</b>	<b>W0014</b>	<b>033</b>	<b>24</b>		<b>27-51-41</b>	<b>ALL</b>
	<b>G</b>	<b>10</b>	<b>2</b>	<b>W0014</b>	<b>039</b>	<b>24</b>		<b>27-58-31</b>	<b>ALL</b>
	<b>G</b>	<b>11</b>	<b>2</b>	<b>W0016</b>	<b>036</b>	<b>24</b>		<b>24-27-21</b>	<b>ALL</b>
	<b>G</b>	<b>11</b>	<b>2</b>	<b>W0016</b>	<b>057</b>	<b>24</b>		<b>24-27-21</b>	<b>ALL</b>
	<b>G</b>	<b>11</b>	<b>2</b>	<b>W0016</b>	<b>058</b>	<b>24</b>		<b>24-27-21</b>	<b>ALL</b>
	<b>G</b>	<b>117</b>	<b>2</b>	<b>W0014</b>	<b>130</b>	<b>24</b>		<b>29-33-11</b>	<b>ALL</b>
	<b>G</b>	<b>117</b>	<b>2</b>	<b>W0014</b>	<b>176</b>	<b>24</b>		<b>29-33-11</b>	<b>ALL</b>
	<b>G</b>	<b>117</b>	<b>2</b>	<b>W0014</b>	<b>177</b>	<b>24</b>		<b>29-33-11</b>	<b>ALL</b>
	<b>G</b>	<b>117</b>	<b>2</b>	<b>W0016</b>	<b>087</b>	<b>24</b>		<b>29-33-11</b>	<b>ALL</b>
	<b>G</b>	<b>124</b>	<b>2</b>	<b>W0014</b>	<b>219B</b>	<b>24</b>		<b>21-31-21</b>	<b>ALL</b>
	<b>G</b>	<b>124</b>	<b>2</b>	<b>W0014</b>	<b>234B</b>	<b>24</b>		<b>27-51-51</b>	<b>ALL</b>
	<b>G</b>	<b>124</b>	<b>2</b>	<b>W0014</b>	<b>240B</b>	<b>24</b>		<b>27-51-51</b>	<b>ALL</b>

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 288

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	G	125	2	W0014	219R	24		21-31-21	ALL
	G	125	2	W0014	234R	24		27-51-51	ALL
	G	125	2	W0014	240R	24		27-51-51	ALL
	G	126	2	W0014	219Z			21-31-21	ALL
	G	126	2	W0014	234Z			27-51-51	ALL
	G	126	2	W0014	240Z			27-51-51	ALL
	G	136	2	W0014	064	24		27-88-11	ALL
	G	136	2	W0014	574	24		27-88-11	ALL
	G	136	2	W0014	575	24		27-88-11	ALL
	G	144	2	W0016	138	24		24-51-51	ALL
	G	144	2	W0016	146	24		24-51-51	ALL
	G	144	2	W0018	078	24		24-51-51	ALL
	G	148	2	W0014	043	24		27-51-51	ALL
	G	148	2	W0014	543	24		27-51-51	ALL
	G	148	2	W0014	544	24		27-51-51	ALL
	G	154	2	W0014	112	22		29-33-11	ALL
	G	154	2	W0014	115	24		29-33-11	ALL
	G	154	2	W0014	510	22		29-33-11	ALL
	G	155	2	W0014	113	24		29-33-11	ALL
	G	155	2	W0014	114	22		29-33-11	ALL
	G	155	2	W0014	514	22		29-33-11	ALL
	G	157	2	W0014	020	24		27-51-61	ALL
	G	157	2	W0014	034	24		27-51-61	ALL
	G	157	2	W0014	070	24		27-51-61	ALL
	G	159	2	W0014	242Z			73-21-14	ALL
	G	159	2	W0016	194	20		73-21-14	ALL
	G	159	2	W0016	223Z			73-21-14	ALL
	G	160	2	W0014	242B	24		73-21-14	ALL
	G	160	2	W0016	223B	24		73-21-14	ALL
	G	160	2	W0016	224B	24		34-12-62	ALL
	G	161	2	W0014	242R	24		73-21-14	ALL
	G	161	2	W0016	223R	24		73-21-14	ALL
	G	161	2	W0016	224R	24		34-12-62	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 289

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	G	162	2	W0018	025	24		24-28-21	ALL
	G	162	2	W0018	028	24		24-28-21	ALL
	G	162	2	W0018	030	24		24-28-21	ALL
	G	163	2	W0018	026	24		24-28-21	ALL
	G	163	2	W0018	063	24		24-28-21	ALL
	G	163	2	W0018	090	24		24-28-21	ALL
	G	164	2	W0016	060	24		24-28-21	ALL
	G	164	2	W0016	061	24		24-28-21	ALL
	G	164	2	W0018	027	24		24-28-21	ALL
	G	165	2	W0014	270R	24		31-35-12	ALL
	G	165	2	W0014	273R	24		28-41-11	ALL
	G	165	2	W0016	235R	24		28-41-11	ALL
	G	165	2	W0098	234R	24		28-41-11	ALL
	G	166	2	W0014	270B	24		31-35-12	ALL
	G	166	2	W0014	273B	24		28-41-11	ALL
	G	166	2	W0016	235B	24		28-41-11	ALL
	G	166	2	W0098	234B	24		28-41-11	ALL
	G	168	2	W0014	243B	24		73-21-14	ALL
	G	168	2	W0014	244B	24		34-12-61	ALL
	G	168	2	W0016	222B	24		73-21-14	ALL
	G	169	2	W0014	243R	24		73-21-14	ALL
	G	169	2	W0014	244R	24		34-12-61	ALL
	G	169	2	W0016	222R	24		73-21-14	ALL
	G	170	2	W0014	243Z			73-21-14	050-099, 153-199, 275-299
	G	170	2	W0016	193	20		73-21-14	050-099, 153-199, 275-299
	G	170	2	W0016	222Z			73-21-14	050-099, 153-199, 275-299
	G	171	2	W0014	086	22		25-31-21	050-099, 150-199, 275-278
	G	171	2	W0018	073	22		25-31-21	050-099, 150-199, 275-278
	G	172	2	W0014	087	22		25-31-21	050-099, 150-199
	G	172	2	W0014	124	22		25-31-21	275-278
	G	172	2	W0018	072	22		25-31-21	050-099, 150-199
	G	172	2	W0018	089	22		25-31-21	275-278
	G	173	2	W0014	272B	24		31-35-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 290

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	G	173	2	W0016	230B	24		77-35-11	ALL
	G	173	2	W0016	231B	24		77-35-11	ALL
	G	173	2	W0016	234B	24		22-33-11	ALL
	G	174	2	W0014	272R	24		31-35-12	ALL
	G	174	2	W0016	230R	24		77-35-11	ALL
	G	174	2	W0016	231R	24		77-35-11	ALL
	G	174	2	W0016	234R	24		22-33-11	ALL
	G	175	2	W0014	271B	24		31-35-12	ALL
	G	175	2	W0016	228B	24		77-35-11	ALL
	G	175	2	W0016	229B	24		77-35-11	ALL
	G	175	2	W0016	233B	24		22-33-11	ALL
	G	176	2	W0014	271R	24		31-35-12	ALL
	G	176	2	W0016	228R	24		77-35-11	ALL
	G	176	2	W0016	229R	24		77-35-11	ALL
	G	176	2	W0016	233R	24		22-33-11	ALL
	G	22	2	W0014	059	24		27-51-11	ALL
	G	22	2	W0014	549	24		27-51-11	ALL
	G	22	2	W0014	550	24		27-51-11	ALL
	G	23	2	W0016	027	22		24-11-21	ALL
	G	23	2	W0016	029	18		24-11-21	ALL
	G	23	2	W0098	072	18		24-11-21	ALL
	G	31	2	W0016	040	20		24-22-21	ALL
	G	31	2	W0016	041	20		24-22-21	ALL
	G	31	2	W0016	104	24		24-22-21	ALL
	G	35	2	W0016	053	20		24-22-22	ALL
	G	35	2	W0016	054	20		24-22-22	ALL
	G	35	2	W0016	109	24		24-22-22	ALL
	G	37	2	W0016	055	22		25-31-11	ALL
	G	37	2	W0018	068	22		25-31-11	ALL
	G	41	2	W0016	031	24		24-11-21	ALL
	G	41	2	W0016	180	24		24-11-21	ALL
	G	41	2	W0016	182	24		24-11-21	ALL
	G	61	2	W0014	567	24		24-51-71	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 291

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	G	61	2	W0018	024	24		24-51-71	ALL
	G	62	2	W0016	038	22		24-51-52	050-099, 150-199
	G	62	2	W0016	161	24		24-51-52	050-099, 150-199
	G	62	2	W0016	162	24		24-51-52	050-099, 150-199
	G	63	2	W0016	163	24		24-51-52	050-099, 150-199
	G	63	2	W0016	164	22		24-51-52	050-099, 150-199
	G	63	2	W0016	165	24		24-51-52	050-099, 150-199
	G	68	2	W0014	030	24		27-58-31	ALL
	G	68	2	W0014	560	24		27-58-31	ALL
	G	68	2	W0016	033	24		31-51-41	ALL
	G	71	2	W0018	009	20		24-22-41	ALL
	G	71	2	W0018	010	20		24-22-41	ALL
	G	71	2	W0018	041	22		24-22-41	ALL
	G	74	2	W0014	080	24		27-51-61	050-099
	G	74	2	W0014	107	24		27-51-61	050-099
	G	74	2	W0014	108	24		27-51-61	050-099
	G	74	2	W0014	128	24		27-51-61	050-099
	G	77	2	W0014	024	24		27-88-11	ALL
	G	77	2	W0014	027	24		27-88-11	ALL
	G	77	2	W0014	040	24		27-88-11	ALL
	G	81	2	W0016	139	22		24-51-51	ALL
	G	81	2	W0018	079	24		24-41-11	ALL
	G	81	2	W0018	088	24		24-41-11	ALL
	G	85	2	W0014	218B	24		21-31-21	ALL
	G	85	2	W0014	235B	24		27-51-51	ALL
	G	85	2	W0016	217B	24		21-31-21	ALL
	G	86	2	W0014	218R	24		21-31-21	ALL
	G	86	2	W0014	235R	24		27-51-51	ALL
	G	86	2	W0016	217R	24		21-31-21	ALL
	G	95	2	W0014	561	24		27-81-11	ALL
	G	95	2	W0014	562	24		27-81-11	ALL
	G	95	2	W0016	177	22		27-81-11	ALL
	G	96	2	W0014	516	22		32-46-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 292

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	G	96	2	W0014	582	22		32-46-11	ALL
	G	96	2	W0014	583	24		32-46-11	ALL
	F	A002	2	W0014	003	22		27-51-11	ALL
	F	A002	2	W0016	002	22		27-51-11	ALL
	F	A003	2	W0014	005	24		27-51-61	ALL
	F	A003	2	W0016	515	24		27-51-61	ALL
	F	A004	2	W0014	007	24		27-51-11	ALL
	F	A004	2	W0016	006	24		27-51-11	ALL
	F	A005	2	W0014	009	24		27-51-11	ALL
	F	A005	2	W0016	008	24		27-51-11	ALL
	F	A006	2	W0014	011	24		27-51-11	ALL
	F	A006	2	W0016	010	24		27-51-11	ALL
	F	A007	2	W0014	013	24		27-51-11	ALL
	F	A007	2	W0016	012	24		27-51-11	ALL
	F	A008	2	W0014	201B	24		27-51-11	ALL
	F	A008	2	W0016	201B	24		27-51-11	ALL
	F	A009	2	W0014	566	24		28-41-11	ALL
	F	A009	2	W0098	019	24		28-41-11	ALL
	F	A012	2	W0016	170	24		31-51-21	150-154, 275
	F	A012	2	W0098	084	24		31-51-21	150-154, 275
	F	A013	2	W0014	052	22		27-81-11	ALL
	F	A013	2	W0016	014	22		27-81-11	ALL
	F	A014	2	W0014	214B	24		27-81-11	ALL
	F	A014	2	W0016	202B	24		27-81-11	ALL
	F	A015	2	W0014	303B	24		27-81-11	ALL
	F	A015	2	W0016	303B	24		27-81-11	ALL
	F	A016	2	W0014	569	24		24-11-11	ALL
	F	A016	2	W0016	023	24		24-11-11	ALL
	F	A017	2	W0014	053	22		27-81-21	ALL
	F	A017	2	W0016	017	22		27-81-21	ALL
	F	A018	2	W0014	215B	24		27-81-21	ALL
	F	A018	2	W0016	203B	24		27-81-21	ALL
	F	A019	2	W0014	304B	24		27-81-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 293

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	A019	2	W0016	304B	24		27-81-21	ALL
	F	A020	2	W0014	304Y	24		27-81-21	ALL
	F	A020	2	W0016	304Y	24		27-81-21	ALL
	F	A021	2	W0014	069	24		29-11-32	ALL
	F	A021	2	W0098	002	24		29-11-32	ALL
	F	A024	2	W0014	083	24		24-27-21	ALL
	F	A024	2	W0018	022	24		24-27-21	ALL
	F	A025	2	W0014	223R	24		21-31-21	ALL
	F	A025	2	W0016	204R	24		21-31-21	ALL
	F	A026	2	W0014	241Z			34-61-14	ALL
	F	A026	2	W0098	235Z			34-61-14	ALL
	F	A027	2	W0014	612	24		31-31-26	ALL
	F	A027	2	W0098	099	24		31-31-26	ALL
	F	A028	2	W0014	082	24		24-22-12	ALL
	F	A028	2	W0018	003	24		24-22-12	ALL
	F	A030	2	W0014	084	24		24-27-21	ALL
	F	A030	2	W0018	023	24		24-27-21	ALL
	F	A032	2	W0018	004	24		24-22-22	ALL
	F	A032	2	W0098	169	24		24-22-22	ALL
	F	A033	2	W0016	051	24		24-22-22	ALL
	F	A033	2	W0018	006	24		24-22-22	ALL
	F	A034	2	W0016	210B	22		24-22-22	ALL
	F	A034	2	W0018	202B	22		24-22-22	ALL
	F	A038	2	W0016	056	22		25-31-11	ALL
	F	A038	2	W0018	069	22		25-31-11	ALL
	F	A039	2	W0014	568	24		24-51-71	ALL
	F	A039	2	W0018	071	24		24-51-71	ALL
	F	A051	2	W0016	167	20		25-31-11	275-276
	F	A051	2	W0098	167	20		25-31-11	275-276
	X	A057	BJ	W0014	269R	22		31-31-22	ALL
	X	A057	BJ	W0016	243R	22		31-31-22	ALL
	X	A058	BJ	W0014	269B	22		31-31-22	ALL
	X	A058	BJ	W0016	243B	22		31-31-22	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 294

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	A059	2	W0014	611	22		31-31-22	ALL
	F	A059	2	W0016	504	22		31-31-22	ALL
	F	A060	2	W0014	088	24		24-51-71	ALL
	F	A060	2	W0014	110	24		24-51-71	ALL
	F	A069	2	W0014	167	24		27-32-11	ALL
	F	A069	2	W0016	115	24		27-32-11	ALL
	F	A070	2	W0016	034	24		31-51-21	150-154, 275
	F	A070	2	W0098	009	24		31-51-21	150-154, 275
	F	A072	2	W0014	458W	22		32-46-11	ALL
	F	A072	2	W0016	454W	22		32-46-11	ALL
	F	A075	2	W0014	119	24		33-24-11	ALL
	F	A075	2	W0016	086	24		33-24-11	ALL
	F	A076	2	W0014	233R	22		77-31-11	ALL
	F	A076	2	W0016	216R	20		77-31-11	ALL
	F	A079	2	W0014	183	24		24-22-11	ALL
	F	A079	2	W0016	125	24		24-22-11	ALL
	F	A080	2	W0014	060	24		27-81-11	ALL
	F	A080	2	W0016	172	22		27-81-11	ALL
	F	A082	2	W0014	146	24		29-33-11	ALL
	F	A082	2	W0016	092	24		29-33-11	ALL
	F	A083	2	W0014	148	24		29-33-11	ALL
	F	A083	2	W0016	094	24		29-33-11	ALL
	F	A084	2	W0016	020	22		24-11-21	ALL
	F	A084	2	W0098	071	20		24-11-21	ALL
	F	A087	2	W0014	218Z			21-31-21	ALL
	F	A087	2	W0016	217Z			21-31-21	ALL
	F	A088	2	W0014	453W	22		32-46-11	ALL
	F	A088	2	W0016	451W	22		32-46-11	ALL
	F	A089	2	W0014	454W	22		32-46-11	ALL
	F	A089	2	W0016	452W	22		32-46-11	ALL
	F	A090	2	W0014	551	24		27-51-11	ALL
	F	A090	2	W0016	147	24		27-51-11	ALL
	F	A091	2	W0014	553	24		27-51-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 295

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	A091	2	W0016	149	24		27-51-11	ALL
	F	A092	2	W0014	565	24		27-51-11	ALL
	F	A092	2	W0016	151	24		27-51-11	ALL
	F	A093	2	W0014	555	24		27-51-11	ALL
	F	A093	2	W0016	153	24		27-51-11	ALL
	F	A094	2	W0014	557	24		27-51-11	ALL
	F	A094	2	W0016	155	24		27-51-11	ALL
	F	A097	2	W0014	055	22		27-81-21	ALL
	F	A097	2	W0016	019	22		27-81-21	ALL
	F	A101	2	W0014	190	20		24-22-22	ALL
	F	A101	2	W0018	060	20		24-22-22	ALL
	F	A102	2	W0014	192	20		24-22-22	ALL
	F	A102	2	W0016	127	20		24-22-22	ALL
	F	A103	2	W0016	129	20		24-22-22	ALL
	F	A103	2	W0018	059	20		24-22-22	ALL
	F	A105	2	W0014	001	22		27-51-11	ALL
	F	A105	2	W0016	003	22		27-51-11	ALL
	F	A106	2	W0014	049	22		27-81-11	ALL
	F	A106	2	W0016	016	22		27-81-11	ALL
	F	A107	2	W0014	198	24		29-11-31	ALL
	F	A107	2	W0016	130	24		29-11-31	ALL
	F	A108	2	W0014	501	24		29-11-31	ALL
	F	A108	2	W0016	133	24		29-11-31	ALL
	F	A109	2	W0014	502	24		24-51-13	ALL
	F	A109	2	W0018	064	22		24-51-13	ALL
	F	A110	2	W0018	035	22		33-16-22	ALL
	F	A110	2	W0098	075	22		33-16-22	ALL
	F	A113	2	W0014	171	24		27-32-21	ALL
	F	A113	2	W0016	119	24		27-32-21	ALL
	F	A114	2	W0014	173	24		27-32-21	ALL
	F	A114	2	W0016	121	24		27-32-21	ALL
	F	A115	2	W0014	251B	22		21-31-21	ALL
	F	A115	2	W0016	225B	20		21-31-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 296

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	D	A116	2	W0014	078	24		21-31-21	ALL
	F	A118	2	W0014	184	20		24-22-12	ALL
	F	A118	2	W0018	058	20		24-22-12	ALL
	F	A119	2	W0014	186	24		24-22-12	ALL
	F	A119	2	W0018	056	24		24-22-12	ALL
	F	A120	2	W0014	188	20		24-22-12	ALL
	F	A120	2	W0018	054	20		24-22-12	ALL
	F	A121	2	W0016	134	24		24-51-23	ALL
	F	A121	2	W0018	066	24		24-51-23	ALL
	F	A123	2	W0016	140	22		24-51-51	ALL
	F	A123	2	W0018	080	22		24-51-51	ALL
	F	A127	2	W0014	241R	24		34-61-14	ALL
	F	A127	2	W0098	235R	24		34-61-14	ALL
	F	A128	2	W0016	220R	24		34-61-24	ALL
	F	A128	2	W0098	236R	24		34-61-24	ALL
	F	A129	2	W0014	222B	24		21-31-21	ALL
	F	A129	2	W0016	221B	24		21-31-21	ALL
	F	A131	2	W0014	457W	22		32-46-11	ALL
	F	A131	2	W0016	453W	22		32-46-11	ALL
	D	A132	2	W0014	577	24		29-11-22	ALL
	D	A133	2	W0014	576	24		27-88-11	ALL
	F	A134	2	W0014	226B	24		24-22-12	ALL
	F	A134	2	W0018	201B	24		24-22-12	ALL
	F	A135	2	W0014	226Z			24-22-12	ALL
	F	A135	2	W0018	201Z			24-22-12	ALL
	R	A139	2	W0016	035	24		24-11-21	ALL
	F	A142	2	W0014	247B	24		77-31-11	ALL
	F	A142	2	W0016	247B	24		77-31-11	ALL
	F	A143	2	W0014	249B	24		77-31-11	ALL
	F	A143	2	W0016	249B	24		77-31-11	ALL
	F	A145	2	W0014	249Z			77-31-11	ALL
	F	A145	2	W0016	249Z			77-31-11	ALL
	F	A146	2	W0014	161	24		28-41-13	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 297

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	A146	2	W0098	097	24		28-41-13	ALL
	F	A147	2	W0014	236R	24		28-41-13	ALL
	F	A147	2	W0098	237R	24		28-41-13	ALL
	F	A156	2	W0014	089	22		29-33-11	ALL
	F	A156	2	W0016	090	22		29-33-11	ALL
	F	A167	2	W0014	274B	24		31-41-35	ALL
	F	A167	2	W0018	205B	24		31-41-35	ALL
	F	A170	2	W0014	243Z			73-21-14	150-152
	F	A170	2	W0016	193	20		73-21-14	150-152
	F	A170	2	W0016	222Z			73-21-14	150-152
	F	A172	2	W0014	124	22		25-31-21	280-299
	F	A172	2	W0018	089	22		25-31-21	280-299
	F	A177	2	W0014	602	24		77-35-11	ALL
	F	A177	2	W0016	191	24		77-35-11	ALL
	F	C002	2	W0014	004	22		27-51-11	ALL
	F	C002	2	W0016	001	22		27-51-11	ALL
	F	C003	2	W0014	006	24		27-51-61	ALL
	F	C003	2	W0016	005	24		27-51-61	ALL
	F	C004	2	W0014	008	24		27-51-11	ALL
	F	C004	2	W0016	007	24		27-51-11	ALL
	F	C005	2	W0014	010	24		27-51-11	ALL
	F	C005	2	W0016	009	24		27-51-11	ALL
	F	C006	2	W0014	012	24		27-51-11	ALL
	F	C006	2	W0016	011	24		27-51-11	ALL
	F	C007	2	W0014	014	24		27-51-11	ALL
	F	C007	2	W0016	013	24		27-51-11	ALL
	F	C008	2	W0014	201R	24		27-51-11	ALL
	F	C008	2	W0016	201R	24		27-51-11	ALL
	F	C009	2	W0014	051	22		27-81-11	ALL
	F	C009	2	W0016	015	22		27-81-11	ALL
	F	C012	2	W0016	171	24		31-51-21	150-154, 275
	F	C012	2	W0098	085	24		31-51-21	150-154, 275
	F	C013	2	W0014	214R	24		27-81-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 298

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	C013	2	W0016	202R	24		27-81-11	ALL
	F	C014	2	W0014	303R	24		27-81-11	ALL
	F	C014	2	W0016	303R	24		27-81-11	ALL
	F	C015	2	W0014	303Y	24		27-81-11	ALL
	F	C015	2	W0016	303Y	24		27-81-11	ALL
	F	C016	2	W0014	621	24		27-81-31	ALL
	F	C016	2	W0016	509	24		27-81-31	ALL
	F	C017	2	W0014	054	22		27-81-21	ALL
	F	C017	2	W0016	018	22		27-81-21	ALL
	F	C018	2	W0014	215R	24		27-81-21	ALL
	F	C018	2	W0016	203R	24		27-81-21	ALL
	F	C019	2	W0014	304R	24		27-81-21	ALL
	F	C019	2	W0016	304R	24		27-81-21	ALL
	F	C020	2	W0014	613	24		31-31-26	ALL
	F	C020	2	W0016	505	24		31-31-26	ALL
	F	C021	2	W0016	114	24		31-51-21	150-154, 275
	F	C021	2	W0098	080	24		31-51-21	150-154, 275
	F	C024	2	W0014	223B	24		21-31-21	ALL
	F	C024	2	W0016	204B	24		21-31-21	ALL
	F	C025	2	W0014	223Z			21-31-21	ALL
	F	C025	2	W0016	204Z			21-31-21	ALL
	F	C026	2	W0014	589	24		27-51-11	ALL
	F	C026	2	W0016	085	24		27-51-11	ALL
	F	C027	2	W0014	081	24		24-22-12	ALL
	F	C027	2	W0018	002	24		24-22-12	ALL
	F	C028	2	W0016	220Z			34-61-24	ALL
	F	C028	2	W0098	236Z			34-61-24	ALL
	F	C032	2	W0016	050	24		24-22-22	ALL
	F	C032	2	W0018	005	24		24-22-22	ALL
	F	C033	2	W0016	210R	22		24-22-22	ALL
	F	C033	2	W0018	202R	22		24-22-22	ALL
	F	C034	2	W0016	210Z			24-22-22	ALL
	F	C034	2	W0018	202Z			24-22-22	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 299

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	C036	2	W0014	086	22		25-31-21	280-299
	F	C036	2	W0018	073	22		25-31-21	280-299
	F	C040	2	W0014	109	24		24-51-71	ALL
	F	C040	2	W0014	117	24		24-51-71	ALL
	F	C050	2	W0014	169	24		27-32-11	ALL
	F	C050	2	W0016	117	24		27-32-11	ALL
	F	C059	2	W0014	032	24		24-51-71	ALL
	F	C059	2	W0018	074	24		24-51-71	ALL
	F	C064	2	W0014	019	22		27-51-61	ALL
	F	C064	2	W0098	108	22		27-51-61	ALL
	F	C069	2	W0014	168	24		27-32-11	ALL
	F	C069	2	W0016	116	24		27-32-11	ALL
	F	C072	2	W0014	458G	22		32-46-11	ALL
	F	C072	2	W0016	454G	22		32-46-11	ALL
	F	C073	2	W0014	044	24		27-51-61	ALL
	F	C073	2	W0098	096	24		27-51-61	ALL
	F	C075	2	W0014	233Z			77-31-11	ALL
	F	C075	2	W0016	216Z			77-31-11	ALL
	F	C076	2	W0014	233B	22		77-31-11	ALL
	F	C076	2	W0016	216B	20		77-31-11	ALL
	F	C082	2	W0014	147	24		29-33-11	ALL
	F	C082	2	W0016	093	24		29-33-11	ALL
	F	C084	2	W0014	162	24		24-27-11	ALL
	F	C084	2	W0018	034	24		24-27-11	ALL
	F	C088	2	W0014	453G	22		32-46-11	ALL
	F	C088	2	W0016	451G	22		32-46-11	ALL
	F	C089	2	W0014	454G	22		32-46-11	ALL
	F	C089	2	W0016	452G	22		32-46-11	ALL
	F	C090	2	W0014	552	24		27-51-11	ALL
	F	C090	2	W0016	148	24		27-51-11	ALL
	F	C091	2	W0014	564	24		27-51-11	ALL
	F	C091	2	W0016	150	24		27-51-11	ALL
	F	C092	2	W0014	554	24		27-51-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 300

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	C092	2	W0016	152	24		27-51-11	ALL
	F	C093	2	W0014	556	24		27-51-11	ALL
	F	C093	2	W0016	154	24		27-51-11	ALL
	F	C094	2	W0014	558	24		27-51-11	ALL
	F	C094	2	W0016	156	24		27-51-11	ALL
	F	C097	2	W0014	056	22		27-81-21	ALL
	F	C097	2	W0016	159	22		27-81-21	ALL
	F	C101	2	W0014	191	24		24-51-31	ALL
	F	C101	2	W0016	128	24		24-51-31	ALL
	F	C102	2	W0014	193	24		24-51-31	ALL
	F	C102	2	W0016	126	24		24-51-31	ALL
	F	C105	2	W0014	002	22		27-51-11	ALL
	F	C105	2	W0016	160	22		27-51-11	ALL
	F	C106	2	W0014	050	22		27-81-11	ALL
	F	C106	2	W0016	157	22		27-81-11	ALL
	F	C107	2	W0014	199	24		29-11-31	ALL
	F	C107	2	W0016	131	24		29-11-31	ALL
	F	C110	2	W0014	170	24		27-32-11	ALL
	F	C110	2	W0016	118	24		27-32-11	ALL
	F	C113	2	W0014	172	24		27-32-21	ALL
	F	C113	2	W0016	120	24		27-32-21	ALL
	F	C114	2	W0014	174	24		27-32-21	ALL
	F	C114	2	W0016	122	24		27-32-21	ALL
	F	C115	2	W0014	251R	22		21-31-21	ALL
	F	C115	2	W0016	225R	20		21-31-21	ALL
	D	C116	2	W0016	124	24		21-31-21	ALL
	F	C118	2	W0014	185	24		24-51-31	ALL
	F	C118	2	W0018	057	24		24-51-31	ALL
	F	C119	2	W0014	187	24		24-51-31	ALL
	F	C119	2	W0018	055	24		24-51-31	ALL
	F	C120	2	W0014	189	24		24-22-12	ALL
	F	C120	2	W0018	053	24		24-22-12	ALL
	F	C123	2	W0016	141	24		24-51-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 301

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	C123	2	W0018	083	24		24-51-31	ALL
	F	C127	2	W0014	241B	24		34-61-14	ALL
	F	C127	2	W0098	235B	24		34-61-14	ALL
	F	C128	2	W0016	220B	24		34-61-24	ALL
	F	C128	2	W0098	236B	24		34-61-24	ALL
	F	C129	2	W0014	222R	24		21-31-21	ALL
	F	C129	2	W0016	221R	24		21-31-21	ALL
	F	C131	2	W0014	457G	22		32-46-11	ALL
	F	C131	2	W0016	453G	22		32-46-11	ALL
	D	C132	2	W0014	574	24		27-88-11	ALL
	D	C133	2	W0014	575	24		27-88-11	ALL
	F	C134	2	W0014	226R	24		24-22-12	ALL
	F	C134	2	W0018	201R	24		24-22-12	ALL
	R	C139	2	W0016	025	24		24-11-21	ALL
	R	C139	2	W0016	174	24		24-11-21	ALL
	F	C141	2	W0014	247R	24		77-31-11	ALL
	F	C141	2	W0016	247R	24		77-31-11	ALL
	F	C142	2	W0014	249R	24		77-31-11	ALL
	F	C142	2	W0016	249R	24		77-31-11	ALL
	F	C143	2	W0014	247Z			77-31-11	ALL
	F	C143	2	W0016	247Z			77-31-11	ALL
	F	C146	2	W0014	197	22		28-41-13	ALL
	F	C146	2	W0098	098	22		28-41-13	ALL
	F	C147	2	W0014	236B	24		28-41-13	ALL
	F	C147	2	W0098	237B	24		28-41-13	ALL
	F	C156	2	W0014	105	22		29-33-11	ALL
	F	C156	2	W0016	088	24		29-33-11	ALL
	F	C167	2	W0014	274R	24		31-41-35	ALL
	F	C167	2	W0018	205R	24		31-41-35	ALL
	F	DED		W0014	019Z			27-51-61	ALL
	F	DED		W0014	044Z			27-51-61	ALL
	F	DED		W0014	198Z			29-11-31	ALL
	F	DED		W0014	199Z			29-11-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 302

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0176		284T0384 (continued)					SHELF/E02/04		ALL
TB0176	D	DIODEBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	F	BACM15C1A (continued)					SHELF/E02/04		ALL
TB0176	G	BACM15C1B (continued)					SHELF/E02/04		ALL
TB0176	R	RESISTORBLOCK-REF284T0124- (continued)					SHELF/E02/04		ALL
TB0176	X	BACM15C3A (continued)					SHELF/E02/04		ALL
TB0176	Z	BACM15C3C (continued)					SHELF/E02/04		275-299
	F	DED		W0014	251Z			21-31-21	ALL
	F	DED		W0014	501Z			29-11-31	ALL
	F	DED		W0014	502Z			24-51-13	ALL
	G	DED		W0016	027Z			24-11-21	ALL
	G	DED		W0016	029Z			24-11-21	ALL
	G	DED		W0016	087Z			29-33-11	ALL
	F	DED		W0016	088Z			29-33-11	ALL
	F	DED		W0016	090Z			29-33-11	ALL
	F	DED		W0016	125Z			24-22-11	ALL
	F	DED		W0016	130Z			29-11-31	ALL
	F	DED		W0016	131Z			29-11-31	ALL
	F	DED		W0016	133Z			29-11-31	ALL
	F	DED		W0016	134Z			24-51-23	ALL
	F	DED		W0016	225Z			21-31-21	ALL
	F	DED		W0018	064Z			24-51-13	ALL
	F	DED		W0018	066Z			24-51-23	ALL
	F	DED		W0098	071Z			24-11-21	ALL
	G	DED		W0098	072Z			24-11-21	ALL
	F	DED		W0098	096Z			27-51-61	ALL
	F	DED		W0098	108Z			27-51-61	ALL
	F	DED		W0098	167Z			25-31-11	275-276
	F	DED		W0098	169Z			24-22-22	ALL
		G044	BJ	W0014	599	22		77-31-11	150-154
		G044	BJ	W0014	616	22		77-31-11	150-154
		G044	BJ	W0014	617	22		77-31-11	150-154
TB0178	N	MRTB20E09					P007-00/ /		ALL
	N	A001	1B	W1052	201R	24		34-22-15	ALL
	N	A001	1B	W1052	A-A			34-22-15	ALL
	N	B001	1B	W1052	201B	24		34-22-15	ALL
	N	B001	1B	W1052	A-B			34-22-15	ALL
	N	C001	1B	W1052	018	24		34-22-15	ALL
	N	C001	1B	W1052	A-C			34-22-15	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 303

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0178</b>	<b>N</b>	<b>MRTB20E09 (continued)</b>					<b>P007-00/ /</b>		<b>ALL</b>
	N	D001	1B	W1052	019	24		34-22-15	ALL
	N	D001	1B	W1052	A-D			34-22-15	ALL
	N	E001	1B	W1052	020	24		34-22-15	ALL
	N	E001	1B	W1052	A-E			34-22-15	ALL
<b>TB0180</b>	<b>N</b>	<b>MRTB20E09</b>					<b>P007-00/ /</b>		<b>ALL</b>
	N	A001	1B	W1054	201R	24		34-22-25	ALL
	N	A001	1B	W1054	A-A			34-22-25	ALL
	N	B001	1B	W1054	201B	24		34-22-25	ALL
	N	B001	1B	W1054	A-B			34-22-25	ALL
	N	C001	1B	W1054	018	24		34-22-25	ALL
	N	C001	1B	W1054	A-C			34-22-25	ALL
	N	D001	1B	W1054	019	24		34-22-25	ALL
	N	D001	1B	W1054	A-D			34-22-25	ALL
	N	E001	1B	W1054	020	24		34-22-25	ALL
	N	E001	1B	W1054	A-E			34-22-25	ALL
<b>TB0182</b>		<b>BACT44B0940U</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0182</b>	<b>D</b>	<b>DIODEBLOCK-REF284T0049-</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0182</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0182</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0182</b>	<b>H</b>	<b>BACM15C2A</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0182</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0182</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P050-00/ /</b>		<b>ALL</b>
<b>TB0182</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P050-00/ /</b>		<b>150-199, 275-299</b>
	Y	A001	BJ	W1078	720	24		21-58-11	ALL
	Y	A001	BJ	W1080	093	24		21-58-11	ALL
	Y	A001	BJ	W1114	115	24		21-58-11	ALL
	Y	A002	BJ	W1078	108	22		21-58-11	ALL
	Y	A002	BJ	W1080	111	22		21-58-11	ALL
	Y	A003	BJ	W1078	170	24		73-21-15	ALL
	Y	A003	BJ	W1080	157	24		73-21-15	ALL
	Y	A003	BJ	W1080	185	24		22-32-13	ALL
	Y	A004	BJ	W1078	179	24		34-61-13	ALL
	Y	A004	BJ	W1078	190	24		34-61-13	ALL
	Y	A004	BJ	W1080	513	24		34-61-23	ALL
	Y	A005	BJ	W1078	178	24		34-61-13	ALL
	Y	A005	BJ	W1078	189	24		34-61-13	ALL
	Y	A005	BJ	W1080	512	24		34-61-23	ALL
	Y	A006	BJ	W1078	169	24		73-21-15	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 304

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0182		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>150-199, 275-299</b>
	Y	A006	BJ	W1080	184	24		22-32-13	ALL
	Y	A006	BJ	W1080	198	24		73-21-15	ALL
	Y	A007	BJ	W1078	763	24		73-21-11	ALL
	Y	A007	BJ	W1114	095	24		73-21-11	ALL
	Y	A007	BJ	W1114	096	24		73-21-11	ALL
	Y	A009	BJ	W1078	180	24		34-61-13	ALL
	Y	A009	BJ	W1078	191	24		34-61-13	ALL
	Y	A009	BJ	W1080	514	24		34-61-23	ALL
	Y	A010	BJ	W1078	182	24		34-61-13	ALL
	Y	A010	BJ	W1078	193	24		34-61-13	ALL
	Y	A010	BJ	W1080	516	24		34-61-23	ALL
	X	A011	BJ	W1078	088	24		73-21-18	ALL
	X	A011	BJ	W1114	058	24		73-21-18	ALL
	X	A012	BJ	W1080	065	24		73-21-18	ALL
	X	A012	BJ	W1114	067	24		73-21-18	ALL
	Y	A013	BJ	W1078	089	24		73-21-18	150-157, 275-276
	Y	A013	BJ	W1080	211R	24		77-12-12	050-099, 162-199, 277-299
	Y	A013	BJ	W1080	218R	24		77-12-12	050-099, 162-199, 277-299
	Y	A013	BJ	W1114	057	24		73-21-18	150-157, 275-276
	Y	A013	BJ	W1114	061	24		73-21-18	150-157, 275-276
	Y	A013	BJ	W1114	213R	24		77-12-12	050-099, 162-199, 277-299
	Y	A013	BJ	W1114	214R	24		77-12-12	050-099, 162-199, 277-299
	Y	A014	BJ	W1080	FRG			77-12-12	050-099, 162-199, 277-299
	Y	A014	BJ	W1114	213F	20		77-12-12	050-099, 162-199, 277-299
	Y	A014	BJ	W1114	FRM			77-12-12	050-099, 162-199, 277-299
	X	A015	BJ	W1078	509	24		21-24-11	050-099, 150-199
	X	A015	BJ	W1080	728	24		21-24-11	050-099, 150-199
	X	A016	BJ	W1078	502	24		21-51-11	ALL
	X	A016	BJ	W1080	524	24		21-51-11	ALL
	Y	A017	BJ	W1078	FRH			77-12-12	050-099, 162-199, 277-299
	Y	A017	BJ	W1114	211F	20		77-12-12	050-099, 162-199, 277-299
	Y	A017	BJ	W1114	FRN			77-12-12	050-099, 162-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 305

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0182		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>150-199, 275-299</b>
	Y	A018	BJ	W1078	211R	24		77-12-12	050-099, 162-199, 277-299
	Y	A018	BJ	W1078	250R	24		77-12-12	050-099, 162-199, 277-299
	Y	A018	BJ	W1114	211R	24		77-12-12	050-099, 162-199, 277-299
	Y	A018	BJ	W1114	212R	24		77-12-12	050-099, 162-199, 277-299
	D	A019	2	W1078	010	24		31-51-42	ALL
	D	A020	2	W1114	029	22		27-61-11	ALL
	D	A021	2	W1080	018	24		21-51-21	050-099, 150-199, 275-276
	D	A022	2	W1080	559	22		27-61-11	150-152
	D	A023	2	W1078	018	24		21-51-11	050-099, 150-199, 275-276
	F	A023	2	W1078	018	24		21-51-11	277-299
	F	A023	2	W1114	032	24		21-51-11	277-299
	D	A024	2	W1078	558	22		34-45-13	150-152
	D	A025	2	W1114	013	22		22-24-11	ALL
	D	A026	2	W1078	135	24		31-51-42	ALL
	X	A027	BJ	W1080	172	22		73-21-11	050-099, 150-199, 275-278
	X	A027	BJ	W1080	172	24		73-21-11	280-299
	X	A027	BJ	W1114	092	24		73-21-11	ALL
	X	A028	BJ	W1078	524	24		21-58-12	ALL
	X	A028	BJ	W1080	098	24		21-58-12	ALL
	X	B011	BJ	W1078	901	24		21-58-11	ALL
	X	B011	BJ	W1080	101	22		21-58-11	ALL
	X	B012	BJ	W1078	518	24		21-51-11	ALL
	X	B012	BJ	W1080	071	24		21-53-12	ALL
	X	B015	BJ	W1078	513	22		21-24-11	050-099, 150-199
	X	B015	BJ	W1080	722	22		21-24-11	050-099, 150-199
	X	B016	BJ	W1078	503	24		21-51-21	ALL
	X	B016	BJ	W1080	526	24		21-51-21	ALL
	X	B027	BJ	W1080	172Z			73-21-11	ALL
	X	B027	BJ	W1114	092Z			73-21-11	ALL
	X	B028	BJ	W1078	525	24		21-58-12	ALL
	X	B028	BJ	W1080	096	24		21-58-12	ALL
	Y	C001	BJ	W1078	709	24		21-51-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 306

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0182		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>150-199, 275-299</b>
	Y	C001	BJ	W1080	020	22		21-51-21	ALL
	Y	C001	BJ	W1080	032	22		21-51-21	ALL
	Y	C001	BJ	W1080	701	22		21-51-21	ALL
	Y	C002	BJ	W1080	091	24		21-58-11	ALL
	Y	C002	BJ	W1080	540	24		21-58-11	ALL
	Y	C002	BJ	W1114	116	24		21-58-11	ALL
	Y	C003	BJ	W1080	173	24		73-21-17	ALL
	Y	C003	BJ	W1080	182	24		73-21-17	ALL
	Y	C003	BJ	W1080	191	24		73-21-17	ALL
	Y	C004	BJ	W1080	542Z			73-21-11	ALL
	Y	C004	BJ	W1080	685Z			73-21-11	ALL
	Y	C004	BJ	W1114	093Z			73-21-11	ALL
	Y	C005	BJ	W1078	167	24		73-21-15	ALL
	Y	C005	BJ	W1080	183	24		73-21-15	ALL
	Y	C005	BJ	W1080	196	24		73-21-15	ALL
	Y	C006	BJ	W1080	542	24		73-21-11	ALL
	Y	C006	BJ	W1080	685	24		73-21-11	ALL
	Y	C006	BJ	W1114	093	24		73-21-11	ALL
	Y	C007	BJ	W1078	763Z			73-21-11	ALL
	Y	C007	BJ	W1114	095Z			73-21-11	ALL
	Y	C007	BJ	W1114	096Z			73-21-11	ALL
	Y	C008	BJ	W1080	064	24		73-21-18	ALL
	Y	C008	BJ	W1114	060	24		73-21-18	050-099, 155-199, 277-299
	Y	C008	BJ	W1114	060A	24		73-21-18	150-154, 275-276
	Y	C008	BJ	W1114	065	24		73-21-18	050-099, 155-199, 277-299
	Y	C008	BJ	W1114	065A	24		73-21-18	150-154, 275-276
	Y	C009	BJ	W1078	181	24		34-61-13	ALL
	Y	C009	BJ	W1078	192	24		34-61-13	ALL
	Y	C009	BJ	W1080	515	24		34-61-23	ALL
	Y	C010	BJ	W1078	013	24		73-21-17	ALL
	Y	C010	BJ	W1078	160	24		73-21-17	ALL
	X	C011	BJ	W1078	067	24		21-53-22	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 307

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0182		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>150-199, 275-299</b>
	X	C011	BJ	W1080	538	24		21-53-22	ALL
	X	C012	BJ	W1078	146	24		73-21-17	ALL
	X	C012	BJ	W1080	158	24		73-21-17	ALL
	Y	C013	BJ	W1080	211B	24		77-12-12	050-099, 162-199, 277-299
	Y	C013	BJ	W1080	218B	24		77-12-12	050-099, 162-199, 277-299
	Y	C013	BJ	W1114	213B	24		77-12-12	050-099, 162-199, 277-299
	Y	C013	BJ	W1114	214B	24		77-12-12	050-099, 162-199, 277-299
	Y	C014	BJ	W1078	089	24		73-21-18	050-099, 162-199, 277-299
	Y	C014	BJ	W1114	057	24		73-21-18	050-099, 162-199, 277-299
	Y	C014	BJ	W1114	061	24		73-21-18	050-099, 162-199, 277-299
	X	C015	BJ	W1078	512	24		21-24-11	050-099, 150-199
	X	C015	BJ	W1080	723	24		21-24-11	050-099, 150-199
	X	C016	BJ	W1080	043	22		21-58-15	ALL
	X	C016	BJ	W1114	113	24		21-58-15	ALL
	Y	C018	BJ	W1078	211B	24		77-12-12	050-099, 162-199, 277-299
	Y	C018	BJ	W1078	250B	24		77-12-12	050-099, 162-199, 277-299
	Y	C018	BJ	W1114	211B	24		77-12-12	050-099, 162-199, 277-299
	Y	C018	BJ	W1114	212B	24		77-12-12	050-099, 162-199, 277-299
	D	C019	2	W1114	044	24		27-58-21	ALL
	D	C019	2	W1114	120	24		27-58-21	ALL
	D	C020	2	W1114	120	24		27-58-21	ALL
	D	C020	2	W1114	134	22		28-31-12	050-099, 162-164
	D	C021	2	W1080	766	24		21-51-21	050-099, 150-199, 275-276
	D	C022	2	W1080	521	22		27-61-11	150-152
	D	C022	2	W1080	560	22		27-61-11	150-152
	D	C023	2	W1114	032	24		21-51-11	050-099, 150-199, 275-276
	D	C024	2	W1080	560	22		27-61-11	150-152
	D	C025	2	W1114	027	24		27-58-21	ALL
	D	C025	2	W1114	119	24		27-58-21	ALL
	D	C026	2	W1080	601	24		31-51-42	150-199, 275-299
	D	C026	2	W1114	119	24		27-58-21	ALL
	X	C027	BJ	W1078	523	24		73-21-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 308

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0182		<b>BACT44B0940U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0182	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>150-199, 275-299</b>
	X	C027	BJ	W1114	094	24		73-21-11	ALL
	X	C028	BJ	W1078	526	24		21-58-12	ALL
	X	C028	BJ	W1080	099	24		21-58-12	ALL
	D	CAP	Y	W1114	134	22		28-31-12	155-157, 165-199, 277-299
	X	D011	BJ	W1078	032	24		21-51-21	ALL
	X	D011	BJ	W1080	030	24		21-51-21	ALL
	X	D012	BJ	W1078	144	24		73-21-17	ALL
	X	D012	BJ	W1080	533	24		73-21-17	ALL
	X	D015	BJ	W1078	510	24		21-24-11	050-099, 150-199
	X	D015	BJ	W1080	724	24		21-24-11	050-099, 150-199
	X	D016	BJ	W1078	114	24		21-51-21	050, 150-154, 275-276
	X	D016	BJ	W1080	003	24		21-51-21	050, 150-154, 275-276
	X	D027	BJ	W1078	523Z			73-21-11	ALL
	X	D027	BJ	W1114	094Z			73-21-11	ALL
	X	D028	BJ	W1078	532	24		21-58-12	ALL
	X	D028	BJ	W1080	543	24		21-58-12	ALL
	X	DED		W1080	158Z			73-21-17	ALL
	Y	DED		W1080	512Z			34-61-23	ALL
	Y	DED		W1080	513Z			34-61-23	ALL
	Y	DED		W1080	514Z			34-61-23	ALL
	Y	DED		W1080	515Z			34-61-23	ALL
	Y	DED		W1080	516Z			34-61-23	ALL
	Y	REF		W1078	211Z			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1078	250Z			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1078	FRH			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1080	211Z			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1080	218Z			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1080	FRG			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1114	211Z			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1114	212Z			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1114	213Z			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1114	214Z			77-12-12	050-099, 162-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 309

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0182		BACT44B0940U (continued)					P050-00/ /		ALL
TB0182	D	DIODEBLOCK-REF284T0049- (continued)					P050-00/ /		ALL
TB0182	F	BACM15C1A (continued)					P050-00/ /		ALL
TB0182	G	BACM15C1B (continued)					P050-00/ /		ALL
TB0182	H	BACM15C2A (continued)					P050-00/ /		ALL
TB0182	X	BACM15C3A (continued)					P050-00/ /		ALL
TB0182	Y	BACM15C3B (continued)					P050-00/ /		ALL
TB0182	Z	BACM15C3C (continued)					P050-00/ /		150-199, 275-299
	Y	REF		W1114	FRM			77-12-12	050-099, 162-199, 277-299
	Y	REF		W1114	FRN			77-12-12	050-099, 162-199, 277-299
TB0186		BACT44B1428U					P033-00/ /		ALL
TB0186	D	DIODEBLOCK-REF284T0189-					P033-00/ /		ALL
TB0186	F	BACM15C1A					P033-00/ /		ALL
TB0186	G	BACM15C1B					P033-00/ /		ALL
TB0186	H	BACM15C2A					P033-00/ /		ALL
TB0186	X	BACM15C3A					P033-00/ /		ALL
TB0186	Y	BACM15C3B					P033-00/ /		ALL
TB0186	Z	BACM15C3C					P033-00/ /		ALL
	Z	20	BJ	W0142	155	20		30-71-21	150-199
	Z	20	BJ	W0142	157	20		30-71-21	150-199
	Z	20	BJ	W0142	158	20		30-71-21	150-199
	Z	20	BJ	W0142	159	20		30-71-21	150-199
	Z	20	BJ	W0142	161	20		30-71-21	150-199
	Z	21	BJ	W0142	084	20		30-71-21	150-199
	Z	21	BJ	W0142	19R	20		30-71-21	150-199
	Z	21	BJ	W0142	701	20		30-71-21	150-199
	Z	21	BJ	W0142	819	22		30-71-21	150-154
	Z	21	BJ	W0142	819	20		30-71-21	155-199
	Z	21	BJ	W0142	820	20		30-71-21	150-199
	Z	22	BJ	W0142	101	20		30-71-21	155-199
	Z	22	BJ	W0142	164	20		30-71-21	155-199
	Z	22	BJ	W0142	695	20		30-71-21	155-199
	Z	22	BJ	W0142	816	20		30-71-21	155-199
	Z	22	BJ	W0142	817	20		30-71-21	155-199
	Z	23	BJ	W0142	171	20		30-71-21	150-199
	Z	23	BJ	W0142	19L	20		30-71-21	050-099, 150-199
	Z	23	BJ	W0142	19M	20		30-71-21	050-099, 150-199
	Z	23	BJ	W0142	19N	20		30-71-21	050-099, 150-199
	Z	23	BJ	W0142	19P	20		30-71-21	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 310

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0186		BACT44B1428U (continued)					P033-00/ /		ALL
TB0186	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0186	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0186	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0186	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0186	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0186	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0186	Z	BACM15C3C (continued)					P033-00/ /		ALL
	Z	23	BJ	W0142	19T	20		30-71-21	050-099, 150-199
	Z	23	BJ	W0142	697	20		30-71-21	050-099, 150-199
	Z	23	BJ	W0142	715	20		30-71-21	050-099, 155-199
	Z	23	BJ	W0142	715	22		30-71-21	150-154
	Z	7	BJ	W0052	020	20		30-71-23	050-099, 150-199, 276-299
	Z	7	BJ	W0142	044	20		30-71-23	050-099, 150-199
	Z	7	BJ	W0142	048	20		30-71-23	050-099, 150-199
	Z	7	BJ	W0142	739	20		30-71-23	050-099, 155-199
	Z	7	BJ	W0142	739	22		30-71-23	150-154, 275-299
	Z	7	BJ	W0142	741	20		30-71-23	050-099, 155-199
	Z	7	BJ	W0142	741	22		30-71-23	150-154, 275-299
	Z	7	BJ	W0142	742	20		30-71-23	050-099, 155-199
	Z	7	BJ	W0142	742	22		30-71-23	150-154, 275-299
	Z	7	BJ	W0142	826	22		30-71-23	275
	Z	8	BJ	W0144	01Y	22		27-62-11	ALL
	Z	8	BJ	W0144	02A	20		27-62-11	ALL
	Z	8	BJ	W0144	02B	22		27-62-11	ALL
	Z	8	BJ	W0144	02M	20		27-62-11	ALL
	Z	8	BJ	W0144	02T	22		27-62-11	ALL
	Z	8	BJ	W0144	03M	22		27-62-11	ALL
	Z	8	BJ	W0144	683	22		27-62-11	ALL
	Z	8	BJ	W0144	797	22		27-62-11	ALL
	X	A001	BJ	W0142	719	24		24-31-11	ALL
	X	A001	BJ	W0146	001	24		24-31-11	ALL
	Y	A003	BJ	W0142	542	20		30-71-22	050-099
	Y	A003	BJ	W0142	542	22		30-71-22	150-199
	Y	A003	BJ	W0142	718	22		30-71-22	150-199
	Y	A003	BJ	W0142	730	20		30-71-22	050-099
	Y	A003	BJ	W0142	730	22		30-71-22	150-199, 275-299
	Y	A003	BJ	W0142	743	22		30-71-22	275-299
	Y	A003	BJ	W0142	818	20		30-71-22	050-099
	Y	A003	BJ	W0142	818	22		30-71-22	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 311

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0186		<b>BACT44B1428U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Y	A003	BJ	W0142	879	20		30-71-22	050-099
	Y	A004	BJ	W0144	01H	22		SPARE	150-154, 275
	Y	A004	BJ	W0144	01J	22		36-11-51	ALL
	Y	A004	BJ	W0144	01L	22		36-11-51	ALL
	Y	A004	BJ	W0144	795	22		36-11-51	ALL
	Y	A005	BJ	W0142	03K	22		21-44-21	ALL
	Y	A005	BJ	W0142	03Q	24		21-44-21	ALL
	Y	A005	BJ	W0142	03T	22		21-44-21	ALL
	Y	A006	BJ	W0142	09Q	22		30-71-23	275-299
	Y	A006	BJ	W0142	712	22		30-71-23	150-154, 275-299
	Y	A006	BJ	W0142	712	20		30-71-23	155-199
	Y	A006	BJ	W0142	737	22		30-71-23	150-154, 275-299
	Y	A006	BJ	W0142	737	20		30-71-23	155-199
	Y	A006	BJ	W0142	887	22		30-71-23	275-299
	Y	A009	BJ	W0142	05B	22		27-62-11	ALL
	Y	A009	BJ	W0142	07X	22		27-62-11	ALL
	Y	A009	BJ	W0144	02R	22		27-62-11	ALL
	Y	A010	BJ	W0142	50L	22		30-34-11	ALL
	Y	A010	BJ	W0144	5AD	22		30-34-11	ALL
	Y	A010	BJ	W0144	604	22		30-34-11	ALL
	Y	A010	BJ	W0144	640	22		30-34-11	ALL
	Y	A011	BJ	W0142	787	22		28-42-12	ALL
	Y	A011	BJ	W0142	790	22		28-42-12	ALL
	Y	A011	BJ	W0142	791	24		28-42-12	ALL
	Y	A011	BJ	W0146	062	22		28-42-12	050-099, 155-199, 276-299
	Y	A011	BJ	W0146	16A	22		28-42-12	150-154, 275
	Y	A012	BJ	W0142	707	20		30-71-21	050-099, 155-199
	Y	A012	BJ	W0142	707	22		30-71-21	150-154, 275-299
	Y	A012	BJ	W0144	104	22		30-71-21	150-154, 275-299
	Y	A012	BJ	W0144	104	20		30-71-21	155-199
	Y	A012	BJ	W0144	107	20		30-71-21	050-099
	Y	A013	BJ	W0142	626	22		30-33-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 312

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0186		BACT44B1428U (continued)					P033-00/ /		ALL
TB0186	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0186	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0186	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0186	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0186	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0186	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0186	Z	BACM15C3C (continued)					P033-00/ /		ALL
	Y	A013	BJ	W0142	862	22		30-33-11	ALL
	Y	A013	BJ	W0142	863	24		30-33-11	ALL
	Y	A014	BJ	W0142	588	22		30-11-11	ALL
	Y	A014	BJ	W0142	814	22		30-11-11	ALL
	Y	A014	BJ	W0142	892	24		30-11-11	ALL
	X	A015	BJ	W0142	628	22		30-31-21	ALL
	X	A015	BJ	W0144	730	22		30-31-21	ALL
	X	A016	BJ	W0142	632	24		30-31-21	ALL
	X	A016	BJ	W0144	736	24		30-31-21	ALL
	Y	A017	BJ	W0142	70D	20		29-11-14	ALL
	Y	A017	BJ	W0144	70D	20		29-11-14	ALL
	Y	A018	BJ	W0142	02H	24		78-36-21	ALL
	Y	A018	BJ	W0142	02J	22		78-36-21	050-099, 150-156, 162-166, 275-299
	Y	A018	BJ	W0142	02J	24		78-36-21	157, 167-199
	Y	A018	BJ	W0142	02K	22		78-36-21	ALL
	D	A019	2	W0142	07P	24		29-11-22	ALL
	D	A019	2	W0144	785	24		29-11-22	ALL
	Y	A020	BJ	W0142	101	20		30-71-21	050-099
	Y	A020	BJ	W0142	162	20		30-71-21	050-099
	Y	A020	BJ	W0142	171	20		30-71-21	050-099
	Y	A020	BJ	W0144	104	20		30-71-21	050-099
	D	A024	2	W0142	07H	22		29-11-22	ALL
	D	A025	2	W0142	07L	24		29-11-22	ALL
	X	B001	BJ	W0142	720	24		24-31-11	ALL
	X	B001	BJ	W0146	002	24		24-31-11	ALL
	X	B002	BJ	W0142	898	24		30-31-11	ALL
	X	B002	BJ	W0144	710	24		30-31-11	ALL
	X	B015	BJ	W0142	644	24		30-31-21	ALL
	X	B015	BJ	W0144	731	24		30-31-21	ALL
	X	B016	BJ	W0142	654	24		30-31-13	ALL
	X	B016	BJ	W0144	123	24		30-31-13	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 313

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0186		<b>BACT44B1428U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	X	C001	BJ	W0142	05E	24		21-53-22	ALL
	X	C001	BJ	W0144	05Q	24		21-53-22	ALL
	X	C002	BJ	W0142	899	24		30-31-11	ALL
	X	C002	BJ	W0144	707	24		30-31-11	ALL
	Y	C003	BJ	W0142	056	22		27-51-11	ALL
	Y	C003	BJ	W0142	754	22		27-51-11	ALL
	Y	C003	BJ	W0142	758	22		27-51-11	ALL
	Y	C004	BJ	W0052	033	20		30-71-23	050-099, 150-199
	Y	C004	BJ	W0142	736	20		30-71-23	050-099, 150-199
	Y	C004	BJ	W0142	738	20		30-71-23	050-099, 150-199
	Y	C005	BJ	W0142	07W	22		27-62-11	ALL
	Y	C005	BJ	W0144	021	24		27-62-11	ALL
	Y	C005	BJ	W0144	798	22		27-62-11	ALL
	Y	C006	BJ	W0052	086	20		30-71-23	276-299
	Y	C006	BJ	W0142	044	22		30-71-23	275-299
	Y	C006	BJ	W0142	048	22		30-71-23	275-299
	Y	C006	BJ	W0142	738	22		30-71-23	275-299
	Y	C006	BJ	W0142	771	22		30-71-23	275
	Y	C009	BJ	W0142	50D	22		30-34-11	ALL
	Y	C009	BJ	W0144	5AC	22		30-34-11	ALL
	Y	C009	BJ	W0144	600	22		30-34-11	ALL
	Y	C009	BJ	W0144	638	22		30-34-11	ALL
	Y	C010	BJ	W0052	087	20		30-71-22	050-099, 155-199
	Y	C010	BJ	W0052	825	20		30-71-22	276-299
	Y	C010	BJ	W0142	733	20		30-71-22	050-099, 155-199
	Y	C010	BJ	W0142	733	22		30-71-22	276-299
	Y	C010	BJ	W0142	763	20		30-71-22	050-099, 155-199
	Y	C010	BJ	W0142	763	22		30-71-22	276-299
	Y	C011	BJ	W0052	031	22		30-71-21	276-299
	Y	C011	BJ	W0142	08P	22		30-71-21	275-299
	Y	C011	BJ	W0142	815	22		30-71-21	275
	Y	C011	BJ	W0144	101	22		30-71-21	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 314

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0186		BACT44B1428U (continued)					P033-00/ /		ALL
TB0186	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0186	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0186	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0186	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0186	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0186	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0186	Z	BACM15C3C (continued)					P033-00/ /		ALL
	Y	C012	BJ	W0142	081	20		30-71-21	050-099, 155-199
	Y	C012	BJ	W0142	081	22		30-71-21	150-154, 275-299
	Y	C012	BJ	W0144	105	20		30-71-21	050-099, 155-199
	Y	C012	BJ	W0144	105	22		30-71-21	150-154, 275-299
	Y	C013	BJ	W0142	587	22		30-11-11	ALL
	Y	C013	BJ	W0142	608	22		30-11-11	ALL
	Y	C013	BJ	W0142	893	24		30-11-11	ALL
	Y	C014	BJ	W0142	652	22		30-31-13	ALL
	Y	C014	BJ	W0142	653	24		30-31-13	ALL
	Y	C014	BJ	W0144	121	22		30-31-13	ALL
	X	C015	BJ	W0142	640	22		30-31-21	ALL
	X	C015	BJ	W0144	732	22		30-31-21	ALL
	X	C016	BJ	W0142	09H	22		29-11-22	ALL
	X	C016	BJ	W0144	04K	22		29-11-22	ALL
	Y	C017	BJ	W0144	06Q	22		27-62-11	ALL
	Y	C017	BJ	W0144	628	22		27-62-11	ALL
	Y	C017	BJ	W0144	682	22		27-62-11	ALL
	Y	C018	BJ	W0142	07T	22		29-11-22	ALL
	Y	C018	BJ	W0144	04L	22		29-11-22	ALL
	Y	C018	BJ	W0144	04R	24		29-11-22	ALL
	Y	C018	BJ	W0144	04U	24		29-11-22	ALL
	D	C019	2	W0144	783	24		29-11-22	ALL
	Y	C020	BJ	W0142	155	20		30-71-21	050-099
	Y	C020	BJ	W0142	705	20		30-71-21	050-099
	Y	C020	BJ	W0142	706	20		30-71-21	050-099
	D	C024	2	W0142	07J	22		27-09-13	ALL
	D	C024	2	W0142	08R	22		29-11-22	ALL
	D	C025	2	W0142	07M	22		27-09-13	ALL
	D	C025	2	W0142	08S	24		29-11-22	ALL
	X	D001	BJ	W0052	033	20		30-71-23	276-299
	X	D001	BJ	W0142	736	22		30-71-23	276-299
	X	D002	BJ	W0142	672	22		30-31-13	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 315

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0186		<b>BACT44B1428U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0186	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	X	D002	BJ	W0144	115	22		30-31-13	ALL
	X	D015	BJ	W0142	643	24		30-31-21	ALL
	X	D015	BJ	W0144	733	24		30-31-21	ALL
	X	D016	BJ	W0142	671	22		30-31-13	ALL
	X	D016	BJ	W0144	122	22		30-31-13	ALL
	Y	DED		W0142	05BZ			27-62-11	ALL
	D	DED		W0142	07HZ			29-11-22	ALL
	D	DED		W0142	07JZ			27-09-13	ALL
	D	DED		W0142	07LZ			29-11-22	ALL
	D	DED		W0142	07MZ			27-09-13	ALL
	D	DED		W0142	07PZ			29-11-22	ALL
	Y	DED		W0142	07WZ			27-62-11	ALL
	Y	DED		W0142	07XZ			27-62-11	ALL
	D	DED		W0142	08RZ			29-11-22	ALL
	D	DED		W0142	08SZ			29-11-22	ALL
	X	DED		W0142	09HZ			29-11-22	ALL
	Y	DED		W0142	50DZ			30-34-11	ALL
	Y	DED		W0142	50LZ			30-34-11	ALL
	X	DED		W0142	643Z			30-31-21	ALL
	X	DED		W0142	671Z			30-31-13	ALL
	X	DED		W0142	672Z			30-31-13	ALL
	Y	DED		W0142	70DZ			29-11-14	ALL
	X	DED		W0142	899Z			30-31-11	ALL
	Y	DED		W0144	04LZ			29-11-22	ALL
	Y	DED		W0144	121Z			30-31-13	ALL
	X	DED		W0144	123Z			30-31-13	ALL
	Y	DED		W0144	5ACZ			30-34-11	ALL
	Y	DED		W0144	5ADZ			30-34-11	ALL
	X	DED		W0144	710Z			30-31-11	ALL
	X	DED		W0144	730Z			30-31-21	ALL
	X	DED		W0144	731Z			30-31-21	ALL
	X	DED		W0144	732Z			30-31-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 316

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0186		BACT44B1428U (continued)					P033-00/ /		ALL
TB0186	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0186	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0186	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0186	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0186	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0186	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0186	Z	BACM15C3C (continued)					P033-00/ /		ALL
	X	DED		W0144	736Z			30-31-21	ALL
	Y	DED		W0146	062Z			28-42-12	050-099, 155-199, 276-299
	Y	DED		W0146	16AZ			28-42-12	150-154, 275
TB0188		BACT44B1428U					P033-00/ /		ALL
TB0188	D	DIODEBLOCK-REF-284T0189-					P033-00/ /		050-099, 150-199
TB0188	F	BACM15C1A					P033-00/ /		ALL
TB0188	G	BACM15C1B					P033-00/ /		ALL
TB0188	H	BACM15C2A					P033-00/ /		ALL
TB0188	X	BACM15C3A					P033-00/ /		ALL
TB0188	Y	BACM15C3B					P033-00/ /		ALL
TB0188	Z	BACM15C3C					P033-00/ /		ALL
	G	10	2	W0142	032	20		27-51-11	ALL
	G	10	2	W0142	886	22		27-51-11	ALL
	Z	13	BJ	W0142	05D	24		22-41-11	ALL
	Z	13	BJ	W0144	04C	22		29-11-22	ALL
	Z	13	BJ	W0144	04D	22		29-11-22	ALL
	Z	13	BJ	W0144	04N	22		29-11-22	ALL
	Z	13	BJ	W0144	04P	24		29-11-22	ALL
	Z	13	BJ	W0144	04T	24		29-11-22	ALL
	Z	13	BJ	W0144	764	22		29-11-22	ALL
	Z	14	BJ	W0142	02Y	24		21-44-21	ALL
	Z	14	BJ	W0142	03J	24		21-44-21	ALL
	Z	14	BJ	W0142	03Y	24		21-44-21	ALL
	Z	14	BJ	W0142	04G	24		21-44-21	ALL
	Z	14	BJ	W0144	789	24		21-44-21	ALL
	Z	15	BJ	W0142	01H	20		30-71-22	050-099
	Z	15	BJ	W0142	04L	20		30-71-22	050-099
	Z	15	BJ	W0142	703	22		30-71-22	275-299
	Z	15	BJ	W0142	704	20		30-71-22	050-099, 155-199
	Z	15	BJ	W0142	704	22		30-71-22	150-154
	Z	15	BJ	W0142	713	22		30-71-22	150-154

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 317

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0188		BACT44B1428U (continued)					P033-00/ /		ALL
TB0188	D	DIODEBLOCK-REF-284T0189- (continued)					P033-00/ /		050-099, 150-199
TB0188	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0188	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0188	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0188	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0188	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0188	Z	BACM15C3C (continued)					P033-00/ /		ALL
	Z	15	BJ	W0142	713	20		30-71-22	155-199
	Z	15	BJ	W0142	729	20		30-71-22	050-099, 155-199
	Z	15	BJ	W0142	729	22		30-71-22	150-154, 275-299
	Z	15	BJ	W0142	743	20		30-71-22	050-099, 155-199
	Z	15	BJ	W0142	743	22		30-71-22	150-154
	Z	15	BJ	W0142	801	20		30-71-22	050-099
	Z	15	BJ	W0142	824	22		30-71-22	150-154
	Z	15	BJ	W0142	824	20		30-71-22	155-199
	Z	15	BJ	W0142	829	20		30-71-22	050-099, 155-199
	Z	15	BJ	W0142	829	22		30-71-22	150-154
	Z	15	BJ	W0142	880	22		30-71-22	275-299
	Z	15	BJ	W0142	882	20		30-71-22	050-099
	Z	15	BJ	W0142	882	22		30-71-22	275-299
	Z	15	BJ	W0142	883	22		30-71-22	150-154
	Z	15	BJ	W0142	883	20		30-71-22	155-199
	Z	16	BJ	W0142	04J	20		30-71-22	050-099
	Z	16	BJ	W0142	04K	20		30-71-22	050-099
	Z	16	BJ	W0142	04M	20		30-71-22	050-099
	Z	16	BJ	W0142	731	20		30-71-22	050-099
	Z	16	BJ	W0142	731	22		30-71-22	150-199, 275-299
	Z	16	BJ	W0142	801	22		30-71-22	275-299
	Z	16	BJ	W0142	824	20		30-71-22	050-099
	Z	16	BJ	W0142	829	22		30-71-22	275-299
	Z	16	BJ	W0142	831	22		30-71-22	150-199
	Z	16	BJ	W0142	853	22		30-71-22	275-299
	Z	16	BJ	W0142	879	22		30-71-22	150-199, 275-299
	Z	16	BJ	W0142	880	20		30-71-22	050-099
	Z	16	BJ	W0142	882	22		30-71-22	150-199
	Z	16	BJ	W0142	883	22		30-71-22	275-299
	Z	23	BJ	W0142	045	22		30-71-23	150-154, 275-299
	Z	23	BJ	W0142	045	20		30-71-23	155-199
	Z	23	BJ	W0142	046	22		30-71-23	150-154, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 318

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0188		<b>BACT44B1428U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>D</b>	<b>DIODEBLOCK-REF-284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0188	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Z	23	BJ	W0142	046	20		30-71-23	155-199
	Z	23	BJ	W0142	09R	20		30-71-23	050-099
	Z	23	BJ	W0142	138	22		30-71-23	275-299
	Z	23	BJ	W0142	709	20		30-71-23	050-099, 150-199
	Z	23	BJ	W0142	709	22		30-71-23	275-299
	Z	23	BJ	W0142	735	20		30-71-23	050-099, 155-199
	Z	23	BJ	W0142	735	22		30-71-23	150-154, 275-299
	Z	23	BJ	W0142	887	20		30-71-23	050-099
	Z	24	BJ	W0142	09Q	20		30-71-23	050-099, 150-199
	Z	24	BJ	W0142	138	20		30-71-23	050-099, 150-199
	Z	24	BJ	W0142	19U	20		30-71-23	050-099, 150-199
	Z	24	BJ	W0142	710	20		30-71-23	050-099, 150-199
	Z	24	BJ	W0142	712	20		30-71-23	050-099
	Z	24	BJ	W0142	887	20		30-71-23	150-199
	G	5	2	W0142	022	18		27-51-11	ALL
	G	5	2	W0142	057	18		27-51-11	ALL
	G	5	2	W0142	059	18		27-51-11	ALL
	Y	A001	BJ	W0144	01G	24		36-11-51	ALL
	Y	A001	BJ	W0144	020	24		36-11-41	ALL
	Y	A001	BJ	W0144	021	24		36-11-51	ALL
	Y	A002	BJ	W0142	173	20		30-71-21	050-099
	Y	A002	BJ	W0142	694	20		30-71-21	050-099
	Y	A002	BJ	W0142	701	22		30-71-21	050-099
	Y	A002	BJ	W0142	715	22		30-71-21	275-299
	Y	A002	BJ	W0142	721	22		30-71-21	275-299
	Y	A002	BJ	W0142	774	22		30-71-21	275-299
	Y	A002	BJ	W0142	819	20		30-71-21	050-099
	Y	A003	BJ	W0142	069	24		32-09-13	ALL
	Y	A003	BJ	W0142	146	24		32-09-13	ALL
	Y	A003	BJ	W0142	803	24		32-09-13	ALL
	Y	A003	BJ	W0144	757	24		32-09-13	ALL
	Y	A004	BJ	W0142	023	22		30-71-21	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 319

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0188		BACT44B1428U (continued)					P033-00/ /		ALL
TB0188	D	DIODEBLOCK-REF-284T0189- (continued)					P033-00/ /		050-099, 150-199
TB0188	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0188	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0188	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0188	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0188	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0188	Z	BACM15C3C (continued)					P033-00/ /		ALL
	Y	A004	BJ	W0142	164	20		30-71-21	050-099, 150-154
	Y	A004	BJ	W0142	687	22		30-71-21	280-299
	Y	A004	BJ	W0142	695	20		30-71-21	050-099
	Y	A004	BJ	W0142	695	22		30-71-21	150-154, 275-278
	Y	A004	BJ	W0142	816	20		30-71-21	050-099
	Y	A004	BJ	W0142	816	22		30-71-21	150-154, 275-299
	Y	A004	BJ	W0142	817	20		30-71-21	050-099
	Y	A004	BJ	W0142	817	22		30-71-21	150-154, 275-299
	X	A006	BJ	W0142	809	24		28-22-11	ALL
	X	A006	BJ	W0146	011	24		28-22-11	ALL
	Y	A008	BJ	W0142	19H	22		32-45-11	275-299
	Y	A008	BJ	W0144	11D	22		32-45-11	275-299
	Y	A008	BJ	W0144	11E	22		32-45-11	275-299
	Y	A009	BJ	W0142	842	22		30-33-11	ALL
	Y	A009	BJ	W0144	555	22		30-33-11	ALL
	Y	A009	BJ	W0144	563	22		30-33-11	ALL
	Y	A011	BJ	W0142	894	22		30-31-11	ALL
	Y	A011	BJ	W0142	896	24		30-31-11	ALL
	Y	A011	BJ	W0144	703	22		30-31-11	ALL
	Y	A012	BJ	W0142	648	22		30-31-23	ALL
	Y	A012	BJ	W0144	132	22		30-31-23	ALL
	Y	A012	BJ	W0144	133	24		30-31-23	ALL
	X	A017	BJ	W0142	06N	24		21-51-13	ALL
	X	A017	BJ	W0144	01D	24		21-51-13	ALL
	X	A018	BJ	W0142	07G	24		29-11-22	ALL
	X	A018	BJ	W0144	03W	24		29-11-22	ALL
	X	A019	BJ	W0142	08S	24		29-11-22	ALL
	X	A019	BJ	W0144	05C	24		29-11-22	ALL
	X	A020	BJ	W0142	07Q	24		29-11-22	ALL
	X	A020	BJ	W0144	05A	24		29-11-22	ALL
	X	A021	BJ	W0142	07U	22		29-11-22	ALL
	X	A021	BJ	W0144	04F	22		29-11-22	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 320

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0188		<b>BACT44B1428U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>D</b>	<b>DIODEBLOCK-REF-284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0188	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	D	A025	2	W0142	42W	22		30-81-11	050-099, 150-199
	X	B006	BJ	W0142	810	24		28-25-11	ALL
	X	B006	BJ	W0146	004	24		28-25-11	ALL
	X	B007	BJ	W0142	154	24		32-09-13	ALL
	X	B007	BJ	W0144	758	24		32-09-13	ALL
	X	B017	BJ	W0142	06P	24		21-51-13	ALL
	X	B017	BJ	W0144	01E	24		21-51-13	ALL
	X	B018	BJ	W0142	08R	22		29-11-22	ALL
	X	B018	BJ	W0144	05B	22		29-11-22	ALL
	X	B019	BJ	W0142	07M	22		27-09-13	ALL
	X	B019	BJ	W0144	05F	22		27-09-13	ALL
	X	B021	BJ	W0142	07V	22		29-11-22	ALL
	X	B021	BJ	W0144	05D	22		29-11-22	ALL
	X	B022	BJ	W0142	18B	24		22-32-13	ALL
	X	B022	BJ	W0144	18B	24		22-32-13	ALL
	Y	C001	BJ	W0142	542	20		30-71-22	050-099
	Y	C001	BJ	W0142	542	22		30-71-22	150-199, 275-299
	Y	C001	BJ	W0142	801	22		30-71-22	150-199
	Y	C001	BJ	W0142	822	20		30-71-22	050-099
	Y	C001	BJ	W0142	822	22		30-71-22	150-199, 275-299
	Y	C001	BJ	W0142	824	22		30-71-22	275-299
	Y	C001	BJ	W0142	878	20		30-71-22	050-099
	Y	C002	BJ	W0142	162	20		30-71-21	150-199
	Y	C002	BJ	W0142	170	20		30-71-21	150-199
	Y	C002	BJ	W0142	721	20		30-71-21	150-199
	Y	C003	BJ	W0142	06R	22		30-71-22	275-299
	Y	C003	BJ	W0142	19H	22		32-45-11	050-099, 150-199
	Y	C003	BJ	W0142	694	22		30-71-22	275-299
	Y	C003	BJ	W0142	703	22		30-71-22	275-299
	Y	C003	BJ	W0144	11D	22		32-45-11	050-099, 150-199
	Y	C003	BJ	W0144	11E	22		32-45-11	050-099, 150-199
	Y	C004	BJ	W0142	19S	20		30-71-21	150-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 321

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0188		BACT44B1428U (continued)					P033-00/ /		ALL
TB0188	D	DIODEBLOCK-REF-284T0189- (continued)					P033-00/ /		050-099, 150-199
TB0188	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0188	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0188	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0188	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0188	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0188	Z	BACM15C3C (continued)					P033-00/ /		ALL
	Y	C004	BJ	W0142	701	22		30-71-21	275-299
	Y	C004	BJ	W0142	819	22		30-71-21	150-154, 275-299
	Y	C004	BJ	W0142	819	20		30-71-21	155-199
	Y	C004	BJ	W0142	820	22		30-71-21	275-299
	X	C006	BJ	W0052	071	22		33-51-11	ALL
	X	C006	BJ	W0144	760	22		33-51-11	ALL
	X	C007	BJ	W0142	02L	24		32-09-13	ALL
	X	C007	BJ	W0144	076	24		32-09-13	ALL
	Y	C009	BJ	W0142	06M	24		32-09-13	ALL
	Y	C009	BJ	W0142	079	24		32-09-13	ALL
	Y	C009	BJ	W0144	084	24		32-09-13	ALL
	Y	C009	BJ	W0144	086	24		32-09-13	ALL
	Y	C011	BJ	W0142	636	22		30-31-21	ALL
	Y	C011	BJ	W0144	726	22		30-31-21	ALL
	Y	C011	BJ	W0144	728	24		30-31-21	ALL
	Y	C012	BJ	W0142	07N	24		29-11-22	ALL
	Y	C012	BJ	W0144	03P	24		29-11-22	ALL
	Y	C012	BJ	W0144	04V	24		29-11-22	ALL
	X	C017	BJ	W0142	06Q	24		21-51-13	ALL
	X	C017	BJ	W0144	01F	24		21-51-13	ALL
	X	C018	BJ	W0142	07J	22		27-09-13	ALL
	X	C018	BJ	W0144	05E	22		27-09-13	ALL
	X	C019	BJ	W0142	03X	24		21-44-21	ALL
	X	C019	BJ	W0144	787	24		21-44-21	ALL
	X	C020	BJ	W0144	609	22		30-34-11	ALL
	X	C020	BJ	W0146	061	22		30-34-11	ALL
	X	C022	BJ	W0142	70T	20		29-11-14	ALL
	X	C022	BJ	W0144	70T	20		29-11-14	ALL
	D	C025	2	W0142	42V	22		30-11-11	050-099, 150-199
	D	C025	2	W0142	595	22		30-11-11	050-099, 150-199
	X	D006	BJ	W0142	073	24		36-11-41	ALL
	X	D006	BJ	W0144	01P	24		36-11-41	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 322

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0188		BACT44B1428U (continued)					P033-00/ /		ALL
TB0188	D	DIODEBLOCK-REF-284T0189- (continued)					P033-00/ /		050-099, 150-199
TB0188	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0188	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0188	H	BACM15C2A (continued)					P033-00/ /		ALL
TB0188	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0188	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0188	Z	BACM15C3C (continued)					P033-00/ /		ALL
	X	D007	BJ	W0142	02M	22		30-31-11	ALL
	X	D007	BJ	W0144	696	22		30-31-11	ALL
	X	D017	BJ	W0142	07F	24		29-11-22	ALL
	X	D017	BJ	W0144	03V	24		29-11-22	ALL
	X	D018	BJ	W0142	07K	24		29-11-22	ALL
	X	D018	BJ	W0144	04W	24		29-11-22	ALL
	X	D019	BJ	W0052	083	24		77-35-11	ALL
	X	D019	BJ	W0142	35A	24		77-35-11	ALL
	X	D020	BJ	W0142	07Y	24		24-51-52	ALL
	X	D020	BJ	W0142	08G	24		24-51-52	ALL
	X	D022	BJ	W0142	70G	20		29-11-14	ALL
	X	D022	BJ	W0144	70G	20		29-11-14	ALL
	X	DED		W0142	02MZ			30-31-11	ALL
	X	DED		W0142	07FZ			29-11-22	ALL
	X	DED		W0142	07GZ			29-11-22	ALL
	X	DED		W0142	07JZ			27-09-13	ALL
	X	DED		W0142	07KZ			29-11-22	ALL
	X	DED		W0142	07MZ			27-09-13	ALL
	Y	DED		W0142	07NZ			29-11-22	ALL
	X	DED		W0142	07QZ			29-11-22	ALL
	X	DED		W0142	07UZ			29-11-22	ALL
	X	DED		W0142	07VZ			29-11-22	ALL
	X	DED		W0142	07YZ			24-51-52	ALL
	X	DED		W0142	08RZ			29-11-22	ALL
	X	DED		W0142	08SZ			29-11-22	ALL
	Y	DED		W0142	636Z			30-31-21	ALL
	Y	DED		W0142	648Z			30-31-23	ALL
	X	DED		W0142	70GZ			29-11-14	ALL
	X	DED		W0142	70TZ			29-11-14	ALL
	X	DED		W0144	01DZ			21-51-13	ALL
	X	DED		W0144	01EZ			21-51-13	ALL
	X	DED		W0144	01FZ			21-51-13	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 323

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0188		<b>BACT44B1428U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>D</b>	<b>DIODEBLOCK-REF-284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0188	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0188	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Y	DED		W0144	555Z			30-33-11	ALL
	Y	DED		W0144	563Z			30-33-11	ALL
	X	DED		W0144	609Z			30-34-11	050-099
	Y	DED		W0144	703Z			30-31-11	ALL
<b>TB0190</b>		<b>BACT44B0910U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>D</b>	<b>DIODEBLOCK-REF284T0188-</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>F</b>	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>G</b>	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>X</b>	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>Z</b>	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	G	1	2	W0192	557	18		27-81-11	ALL
	G	1	2	W0192	561	18		27-81-11	ALL
	G	1	2	W0192	563	18		27-81-11	ALL
	F	A002	2	W0058	013	16		23-34-11	ALL
	F	A002	2	W0192	087	16		23-34-11	ALL
	X	A003	BJ	W0192	80K	24		21-26-21	050-099, 155-199, 276-299
	X	A003	BJ	W1118	70B	24		21-26-21	050-099, 155-199, 276-299
	X	A004	BJ	W0192	571	22		27-81-11	ALL
	X	A004	BJ	W1118	048	22		27-81-11	ALL
	Y	A005	BJ	W0192	550	24		29-21-31	ALL
	Y	A005	BJ	W0198	032	24		29-21-31	ALL
	F	A009	2	W0058	050	16		33-45-11	ALL
	F	A009	2	W0192	02A	16		33-45-11	ALL
	Y	A011	BJ	W0192	0AE	22		36-11-62	050-099, 150-155, 162-165, 275-276
	Y	A011	BJ	W0192	0AF	22		36-11-62	050-099, 150-155, 162-165, 275-276
	Y	A011	BJ	W0192	680	22		36-11-62	050-099, 150-155, 162-165, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 324

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0190		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	A011	BJ	W0192	72D	22		36-11-62	050-099, 150-155, 162-165, 275-276
	D	A012	2	W0192	125	24		29-11-12	ALL
	Y	A016	BJ	W0192	224R	24		32-42-11	ALL
	Y	A016	BJ	W0192	236R	24		32-42-11	ALL
	Y	A016	BJ	W0198	205R	24		32-42-11	ALL
	F	A017	2	W0058	041	22		30-71-21	275
	F	A017	2	W1118	143	22		30-71-21	275
	X	A018	BJ	W0058	089	20		21-66-41	050-099, 150, 152-199
	X	A018	BJ	W0192	75U	20		21-66-41	050-099, 150, 152-199
	X	B003	BJ	W0192	551	24		29-21-31	ALL
	X	B003	BJ	W0198	040	24		29-21-31	ALL
	X	B004	BJ	W0192	572	22		27-81-11	ALL
	X	B004	BJ	W1118	027	22		27-81-11	ALL
	X	B013	BJ	W0058	045	22		30-71-22	275
	X	B013	BJ	W1118	147	22		30-71-22	275
	X	B018	BJ	W0058	088	20		21-66-41	050-099, 150, 152-199
	X	B018	BJ	W0192	761	20		21-66-41	050-099, 150, 152-199
	X	B019	BJ	W0058	087	20		21-66-41	050-099, 150, 152-199
	X	B019	BJ	W0192	76H	20		21-66-41	050-099, 150, 152-199
	F	C002	2	W0058	014	16		23-34-11	ALL
	F	C002	2	W0192	088	16		23-34-11	ALL
	X	C003	BJ	W0192	552	24		29-21-31	ALL
	X	C003	BJ	W0198	035	24		29-21-31	ALL
	Y	C005	BJ	W0192	0AK	24		36-21-11	050-099, 150-155, 163-165, 275-276
	Y	C005	BJ	W0192	0AL	24		36-21-11	050-099, 150-155, 163-165, 275-276
	Y	C005	BJ	W0192	526	24		36-21-11	050-099, 150-155, 162-165, 275-276
	Y	C006	BJ	W0198	063	20		49-61-11	ALL
	Y	C006	BJ	W0198	531	22		49-61-11	ALL
	Y	C006	BJ	W0198	532	22		49-61-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 325

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0190		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	F	C008	2	W0192	570	22		27-81-11	ALL
	F	C008	2	W1118	047	22		27-81-11	ALL
	F	C009	2	W0058	051	16		33-45-11	ALL
	F	C009	2	W0192	02C	16		33-45-11	ALL
	Y	C010	BJ	W0188	015	24		24-22-11	ALL
	Y	C010	BJ	W0192	509	24		24-22-21	ALL
	Y	C010	BJ	W0198	049	24		24-22-41	ALL
	Y	C011	BJ	W0192	0AG	22		36-11-62	050-099, 150-155, 162-165, 275-276
	Y	C011	BJ	W0192	0AH	22		36-11-62	050-099, 150-155, 162-165, 275-276
	Y	C011	BJ	W0192	681	22		36-11-62	050-099, 150-155, 162-165, 275-276
	Y	C011	BJ	W0192	72E	22		36-11-62	050-099, 150-155, 162-165, 275-276
	D	C012	2	W0192	11M	22		29-11-12	ALL
	D	C012	2	W0192	126	22		29-11-12	ALL
	X	C013	BJ	W0188	068	24		36-11-41	ALL
	X	C013	BJ	W0192	807	24		36-11-41	ALL
	X	C014	BJ	W0192	742	22		26-15-12	ALL
	X	C014	BJ	W0198	064	22		26-15-12	ALL
	Y	C015	BJ	W0192	224Z			32-42-11	ALL
	Y	C015	BJ	W0192	236Z			32-42-11	ALL
	Y	C015	BJ	W0198	205Z			32-42-11	ALL
	Y	C016	BJ	W0192	224B	24		32-42-11	ALL
	Y	C016	BJ	W0192	236B	24		32-42-11	ALL
	Y	C016	BJ	W0198	205B	24		32-42-11	ALL
	F	C017	2	W0058	083	18		21-66-41	050-099, 150, 152-199
	F	C017	2	W0192	75E	18		21-66-41	050-099, 150, 152-199
	X	C018	BJ	W0058	043	20		30-71-22	275
	X	C018	BJ	W1118	145	20		30-71-22	275
	X	C019	BJ	W0058	044	20		30-71-22	275
	X	C019	BJ	W1118	146	20		30-71-22	275

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 326

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0190		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0190	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	D004	BJ	W0058	081	22		21-66-41	050-099, 150, 152-199
	X	D004	BJ	W0192	75H	22		21-66-41	050-099, 150, 152-199
	X	D013	BJ	W0188	114	24		21-26-11	ALL
	X	D013	BJ	W0192	02R	24		21-26-11	150-154, 275
	X	D013	BJ	W0192	80T	24		21-26-11	050-099, 155-199, 276-299
	X	D014	BJ	W0058	042	22		30-71-22	275
	X	D014	BJ	W1118	144	22		30-71-22	275
	X	DED		W0192	02RZ			21-26-11	150-154, 275
	D	DED		W0192	11MZ			29-11-12	ALL
	D	DED		W0192	125Z			29-11-12	ALL
	D	DED		W0192	126Z			29-11-12	ALL
	Y	DED		W0192	550Z			29-21-31	ALL
	X	DED		W0192	551Z			29-21-31	ALL
	X	DED		W0192	552Z			29-21-31	ALL
	Y	DED		W0198	032Z			29-21-31	ALL
	X	DED		W0198	035Z			29-21-31	ALL
	X	DED		W0198	040Z			29-21-31	ALL
	F	DED		W1118	047Z			27-81-11	ALL
<b>TB0192</b>		<b>BACT44B0910U</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0192</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0192</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0192</b>	<b>H</b>	<b>BACM15C2A</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0192</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0192</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0192</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	16	BJ	W0192	501	24		21-58-16	050-099, 155-199, 276-299
	Z	16	BJ	W0192	588	24		21-58-16	050-099, 155-199, 276-299
	Z	16	BJ	W0192	749	24		21-26-11	050-099, 155-199, 276-299
	Z	16	BJ	W0192	758	24		21-26-11	050-099, 155-199, 276-299
	Z	16	BJ	W0192	80M	24		21-26-11	050-099, 155-199, 276-299
	Z	17	BJ	W0188	081	24		22-41-11	ALL
	Z	17	BJ	W0192	07T	24		29-11-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 327

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0192		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	F	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	G	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	H	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	17	BJ	W0192	20C	20		29-11-14	ALL
	Z	17	BJ	W0192	790	22		29-11-12	ALL
	Z	17	BJ	W0192	801	22		29-11-12	ALL
	Z	17	BJ	W0192	837	22		29-11-12	ALL
	G	20	2	W0192	822	18		30-71-11	ALL
	G	20	2	W0192	823	18		30-71-11	ALL
	G	20	2	W1118	155	20		30-71-11	ALL
	X	A001	BJ	W0188	139	24		21-45-21	ALL
	X	A001	BJ	W0192	19J	24		21-45-21	ALL
	F	A003	2	W0058	084	18		21-66-41	050-099, 150, 152-199
	F	A003	2	W0192	75F	18		21-66-41	050-099, 150, 152-199
	X	A004	BJ	W0188	017	24		21-53-22	ALL
	X	A004	BJ	W0192	751	24		21-53-22	ALL
	Y	A006	BJ	W0188	125	24		36-11-41	ALL
	Y	A006	BJ	W0192	805	24		36-11-41	ALL
	X	A008	BJ	W0058	018	20		21-45-11	ALL
	X	A008	BJ	W0192	740	20		21-45-11	ALL
	X	A010	BJ	W0192	05V	22		74-31-21	ALL
	X	A010	BJ	W0198	190	22		74-31-21	ALL
	X	A011	BJ	W0198	622	20		25-31-12	153-154
	X	A011	BJ	W1118	103	20		25-33-11	153-154
	Y	A012	BJ	W0192	04P	22		21-61-11	ALL
	Y	A012	BJ	W0192	527	22		21-61-11	ALL
	Y	A012	BJ	W0192	732	22		21-61-11	ALL
	Y	A012	BJ	W0192	765	22		21-61-11	ALL
	Y	A013	BJ	W0192	01W	24		21-25-21	ALL
	Y	A013	BJ	W0192	150	24		21-25-21	ALL
	Y	A013	BJ	W0192	152	24		21-25-21	ALL
	Y	A013	BJ	W0192	724	24		21-25-21	ALL
	Y	A015	BJ	W0058	029	20		23-32-11	ALL
	Y	A015	BJ	W0192	797	20		23-32-11	ALL
	Y	A015	BJ	W0192	798	20		23-32-11	050-099, 150-199
	X	A018	BJ	W0058	030	20		23-32-11	050-099, 150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 328

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0192		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	F	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	G	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	H	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	A018	BJ	W0192	799	20		23-32-11	050-099, 150-199
	X	B002	BJ	W0192	746	24		21-51-11	ALL
	X	B002	BJ	W1118	12J	24		21-51-11	ALL
	X	B008	BJ	W0058	019	20		21-45-11	ALL
	X	B008	BJ	W0192	138	20		21-45-11	ALL
	X	B009	BJ	W0188	70D	20		29-11-14	ALL
	X	B009	BJ	W0192	20D	20		29-11-14	ALL
	X	B010	BJ	W0192	05X	22		74-31-21	ALL
	X	B010	BJ	W0198	191	22		74-31-21	ALL
	X	B018	BJ	W0058	031	20		23-32-11	050-099, 150-199
	X	B018	BJ	W0192	800	20		23-32-11	050-099, 150-199
	X	B019	BJ	W0192	630	24		23-31-13	ALL
	X	B019	BJ	W0198	147	24		23-31-13	ALL
	X	C001	BJ	W0188	038	24		21-58-11	ALL
	X	C001	BJ	W0192	194	24		21-58-11	ALL
	X	C002	BJ	W0192	01P	22		21-26-21	ALL
	X	C002	BJ	W1118	077	22		21-26-21	ALL
	F	C003	2	W0058	004	22		33-21-21	ALL
	F	C003	2	W0192	788	22		33-21-21	ALL
	X	C004	BJ	W0192	078	24		31-31-22	ALL
	X	C004	BJ	W0198	029	24		31-31-22	ALL
	X	C005	BJ	W0192	177	22		21-26-21	ALL
	X	C005	BJ	W1118	156	22		21-26-21	ALL
	Y	C007	BJ	W0192	501	24		21-58-16	150-154, 275
	Y	C007	BJ	W0192	588	24		21-58-16	150-154, 275
	Y	C007	BJ	W0192	749	24		21-26-11	150-154, 275
	Y	C007	BJ	W0192	758	24		21-26-11	150-154, 275
	X	C008	BJ	W0188	132	24		27-51-61	ALL
	X	C008	BJ	W0192	12Z	24		27-51-61	ALL
	X	C010	BJ	W0192	606	22		74-31-21	ALL
	X	C010	BJ	W0198	192	22		74-31-21	ALL
	X	C011	BJ	W0058	039	20		30-41-12	ALL
	X	C011	BJ	W1118	100	20		30-41-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 329

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0192		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0192	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	C012	BJ	W0192	047	24		21-25-21	ALL
	Y	C012	BJ	W0192	19P	24		21-45-21	ALL
	Y	C012	BJ	W0192	19R	24		21-25-21	ALL
	Y	C013	BJ	W0198	124	20		76-11-11	ALL
	Y	C013	BJ	W0198	126	20		76-11-11	ALL
	Y	C013	BJ	W0198	524	24		76-11-11	ALL
	Y	C015	BJ	W0192	615	20		33-42-11	ALL
	Y	C015	BJ	W0192	826	20		33-42-11	ALL
	Y	C015	BJ	W0192	830	20		33-42-11	ALL
	X	C018	BJ	W0192	80L	24		21-26-21	050-099, 155-199, 276-299
	X	C018	BJ	W1118	157	24		21-26-21	050-099, 155-199, 276-299
	X	C019	BJ	W0198	623	20		25-31-12	153-154
	X	C019	BJ	W1118	558	20		25-31-12	153-154
	X	D005	BJ	W0188	131	24		27-51-61	ALL
	X	D005	BJ	W0192	12Y	24		27-51-61	ALL
	X	D008	BJ	W0198	599	20		25-33-11	050-099, 155-199, 277-299
	X	D008	BJ	W1118	511	20		25-33-11	050-099, 155-199, 277-299
	X	D010	BJ	W0192	607	22		74-31-21	ALL
	X	D010	BJ	W0198	193	22		74-31-21	ALL
	X	D011	BJ	W0058	040	20		30-41-12	ALL
	X	D011	BJ	W1118	101	20		30-41-12	ALL
	X	D019	BJ	W0058	034	22		21-26-21	ALL
	X	D019	BJ	W1118	072	22		21-26-21	ALL
	X	DED		W0192	05XZ			74-31-21	ALL
	X	DED		W0192	607Z			74-31-21	ALL
	X	DED		W0198	191Z			74-31-21	ALL
	X	DED		W0198	193Z			74-31-21	ALL
	X	DED		W0198	599Z			25-33-11	050-099, 155-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 330

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0196		BACT44B1948U					P033-00/ /		ALL
TB0196	D	DIODEBLOCK-REF284T0189-					P033-00/ /		ALL
TB0196	F	BACM15C1A					P033-00/ /		ALL
TB0196	G	BACM15C1B					P033-00/ /		ALL
TB0196	H	BACB15C2A					P033-00/ /		ALL
TB0196	X	BACM15C3A					P033-00/ /		ALL
TB0196	Y	BACM15C3B					P033-00/ /		ALL
TB0196	Z	BACM15C3C					P033-00/ /		ALL
	G	10	2	W0052	031	18		30-71-21	050-099, 150-199
	G	10	2	W0142	08P	18		30-71-21	050-099, 150-199
	G	10	2	W0144	101	20		30-71-21	050-099, 150-199
	Z	5	BJ	W0142	080	24		32-09-13	ALL
	Z	5	BJ	W0142	26R	22		27-62-11	ALL
	Z	5	BJ	W0142	26S	22		27-62-11	ALL
	Z	5	BJ	W0144	074	24		32-09-13	ALL
	Z	5	BJ	W0144	083	24		32-09-13	ALL
	Z	5	BJ	W0144	085	24		32-09-13	ALL
	Z	5	BJ	W0144	615	24		32-09-13	ALL
	Y	A001	BJ	W0142	805	22		27-62-11	ALL
	Y	A001	BJ	W0144	03A	22		27-62-11	ALL
	Y	A001	BJ	W0144	06P	22		27-62-11	ALL
	Y	A002	BJ	W0142	016	22		23-34-11	ALL
	Y	A002	BJ	W0144	013	22		23-34-11	ALL
	Y	A002	BJ	W0144	178	22		23-34-11	ALL
	X	A003	BJ	W0142	806	22		27-62-11	ALL
	X	A003	BJ	W0144	03B	22		27-62-11	ALL
	Y	A007	BJ	W0142	02R	22		30-32-11	ALL
	Y	A007	BJ	W0144	07V	22		30-32-11	ALL
	Y	A007	BJ	W0144	522	22		30-32-11	ALL
	Y	A008	BJ	W0144	70E	20		29-11-14	ALL
	Y	A008	BJ	W0144	70I	20		29-11-14	ALL
	Y	A008	BJ	W0144	70J	20		29-11-14	ALL
	Y	A008	BJ	W0144	70V	20		29-11-14	ALL
	F	A009	2	W0052	067	16		33-45-11	ALL
	F	A009	2	W0142	866	16		33-45-11	ALL
	Y	A011	BJ	W0144	015	22		23-34-11	ALL
	Y	A011	BJ	W0144	016	22		23-34-11	ALL
	Y	A011	BJ	W0144	045	24		23-34-12	ALL
	Y	A011	BJ	W0144	138	22		23-34-11	ALL
	Y	A012	BJ	W0144	034	24		27-58-11	ALL
	Y	A012	BJ	W0144	147	24		27-58-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 331

Mar 14/2007





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0196		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>H</b>	<b>BACB15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Y	A012	BJ	W0144	202R	24		31-31-13	ALL
	F	A013	2	W0142	71C	20		29-11-14	ALL
	F	A013	2	W0144	71C	20		29-11-14	ALL
	X	A014	BJ	W0052	016	22		52-11-11	ALL
	X	A014	BJ	W0142	102	22		52-11-11	ALL
	X	A015	BJ	W0142	860	22		30-33-11	ALL
	X	A015	BJ	W0144	565	22		30-33-11	ALL
	X	A016	BJ	W0142	02T	24		21-51-13	ALL
	X	A016	BJ	W0144	01A	24		21-51-13	ALL
	X	A017	BJ	W0142	05I	24		21-53-22	ALL
	X	A017	BJ	W0144	05X	24		21-53-22	ALL
	X	A018	BJ	W0142	204R	22		21-51-22	ALL
	X	A018	BJ	W0144	204R	22		21-51-22	ALL
	X	A019	BJ	W0052	821	20		30-71-22	050-099, 155-199, 276-299
	X	A019	BJ	W0142	16A	20		30-71-22	050-099, 155-199, 276-299
	D	A020	2	W0144	01M	22		36-11-51	ALL
	D	A021	2	W0144	05G	22		32-41-11	ALL
	D	A022	2	W0144	767	24		29-11-12	ALL
	D	A023	2	W0144	04J	24		29-11-22	ALL
	D	A023	2	W0144	768	24		29-11-22	ALL
	D	A024	2	W0144	04B	22		29-11-22	ALL
	D	A025	2	W0142	066	22		23-34-11	ALL
	D	A025	2	W0144	139	22		23-34-11	ALL
	X	B003	BJ	W0052	054	20		33-22-11	ALL
	X	B003	BJ	W0142	123	20		33-22-11	ALL
	X	B014	BJ	W0052	017	22		52-11-11	ALL
	X	B014	BJ	W0142	103	22		52-11-11	ALL
	X	B015	BJ	W0142	861	22		30-33-11	ALL
	X	B015	BJ	W0144	556	22		30-33-11	ALL
	X	B016	BJ	W0142	02U	24		21-51-13	ALL
	X	B016	BJ	W0144	01B	24		21-51-13	ALL
	X	B017	BJ	W0142	05J	24		21-53-22	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 332

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0196		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>H</b>	<b>BACB15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0196	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	X	B017	BJ	W0144	06L	24		21-53-22	ALL
	X	B018	BJ	W0142	204B	22		21-51-22	ALL
	X	B018	BJ	W0144	204B	22		21-51-22	ALL
	X	B019	BJ	W0052	838	20		30-71-22	050-099, 155-199
	X	B019	BJ	W0052	838	22		30-71-22	276-299
	X	B019	BJ	W0142	17A	22		30-71-22	276-299
	X	B019	BJ	W0142	732	20		30-71-22	050-099
	X	B019	BJ	W0142	732	22		30-71-22	155-199
	X	C003	BJ	W0142	667	22		30-31-23	ALL
	X	C003	BJ	W0144	128	22		30-31-23	ALL
	X	C004	BJ	W0142	08H	24		24-51-52	ALL
	X	C004	BJ	W0142	889	24		24-51-52	ALL
	Y	C007	BJ	W0142	02S	22		30-32-11	ALL
	Y	C007	BJ	W0144	521	22		30-32-11	ALL
	Y	C007	BJ	W0144	534	22		30-32-11	ALL
	Y	C008	BJ	W0142	70C	20		29-11-14	ALL
	Y	C008	BJ	W0144	70R	20		29-11-14	ALL
	Y	C008	BJ	W0144	70S	20		29-11-14	ALL
	Y	C008	BJ	W0144	70V	20		29-11-14	ALL
	F	C009	2	W0052	068	16		33-45-11	ALL
	F	C009	2	W0142	867	16		33-45-11	ALL
	Y	C011	BJ	W0144	035	24		27-58-11	ALL
	Y	C011	BJ	W0144	146	24		27-58-11	ALL
	Y	C011	BJ	W0144	202B	24		31-31-13	ALL
	Y	C012	BJ	W0142	850	22		30-32-21	ALL
	Y	C012	BJ	W0144	134	22		30-32-21	ALL
	Y	C012	BJ	W0144	135	24		30-32-21	ALL
	F	C013	2	W0142	71H	20		29-11-14	ALL
	F	C013	2	W0144	71H	20		29-11-14	ALL
	X	C014	BJ	W0142	657	24		30-31-23	ALL
	X	C014	BJ	W0144	130	24		30-31-23	ALL
	X	C015	BJ	W0142	841	22		30-33-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0100

Page 333

Mar 14/2007



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0196		BACT44B1948U (continued)					P033-00/ /		ALL
TB0196	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0196	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0196	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0196	H	BACB15C2A (continued)					P033-00/ /		ALL
TB0196	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0196	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0196	Z	BACM15C3C (continued)					P033-00/ /		ALL
	X	C015	BJ	W0144	559	22		30-33-11	ALL
	X	C016	BJ	W0142	02V	24		21-51-13	ALL
	X	C016	BJ	W0144	01C	24		21-51-13	ALL
	X	C017	BJ	W0142	203R	22		21-51-22	ALL
	X	C017	BJ	W0144	203R	22		21-51-22	ALL
	X	C018	BJ	W0142	70K	20		29-11-14	ALL
	X	C018	BJ	W0144	70K	20		29-11-14	ALL
	X	C019	BJ	W0052	087	22		30-71-22	276-299
	X	C019	BJ	W0142	732	22		30-71-22	276-299
	D	C020	2	W0144	01K	22		36-11-51	ALL
	D	C021	2	W0144	04P	24		29-11-22	ALL
	D	C022	2	W0144	053	22		76-11-11	ALL
	D	C022	2	W0144	05H	24		76-11-11	ALL
	D	C023	2	W0144	04R	24		29-11-22	ALL
	D	C024	2	W0144	04N	22		29-11-22	ALL
	D	C025	2	W0142	065	22		23-34-11	ALL
	D	C025	2	W0144	138	22		23-34-11	ALL
	X	D003	BJ	W0142	670	22		30-31-23	ALL
	X	D003	BJ	W0144	129	22		30-31-23	ALL
	X	D004	BJ	W0142	02N	22		30-31-11	ALL
	X	D004	BJ	W0144	709	22		30-31-11	ALL
	X	D014	BJ	W0052	018	22		52-11-11	ALL
	X	D014	BJ	W0142	104	22		52-11-11	ALL
	X	D015	BJ	W0142	05F	24		21-53-22	ALL
	X	D015	BJ	W0144	05T	24		21-53-22	ALL
	X	D016	BJ	W0142	05H	24		21-53-22	ALL
	X	D016	BJ	W0144	06I	24		21-53-22	ALL
	X	D017	BJ	W0142	203B	22		21-51-22	ALL
	X	D017	BJ	W0144	203B	22		21-51-22	ALL
	X	D018	BJ	W0142	70M	20		29-11-14	ALL
	X	D018	BJ	W0144	70M	20		29-11-14	ALL
	X	D019	BJ	W0052	825	20		30-71-21	050-099, 155-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 334

Mar 14/2007



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0196		BACT44B1948U (continued)					P033-00/ /		ALL
TB0196	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0196	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0196	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0196	H	BACB15C2A (continued)					P033-00/ /		ALL
TB0196	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0196	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0196	Z	BACM15C3C (continued)					P033-00/ /		ALL
	X	D019	BJ	W0142	20B	20		30-71-21	050-099, 155-199
	X	DED		W0142	02NZ			30-31-11	ALL
	Y	DED		W0142	02RZ			30-32-11	ALL
	Y	DED		W0142	02SZ			30-32-11	ALL
	X	DED		W0142	657Z			30-31-23	ALL
	Y	DED		W0142	70CZ			29-11-14	ALL
	F	DED		W0142	71CZ			29-11-14	ALL
	F	DED		W0142	71HZ			29-11-14	ALL
	Y	DED		W0142	805Z			27-62-11	ALL
	X	DED		W0142	806Z			27-62-11	ALL
	Y	DED		W0142	850Z			30-32-21	ALL
	X	DED		W0142	860Z			30-33-11	ALL
	X	DED		W0142	861Z			30-33-11	ALL
	X	DED		W0144	01AZ			21-51-13	ALL
	X	DED		W0144	01BZ			21-51-13	ALL
	X	DED		W0144	01CZ			21-51-13	ALL
	D	DED		W0144	05GZ			32-41-11	ALL
	X	DED		W0144	128Z			30-31-23	ALL
	X	DED		W0144	129Z			30-31-23	ALL
	X	DED		W0144	203Z			21-51-22	ALL
	X	DED		W0144	204Z			21-51-22	ALL
	X	DED		W0144	559Z			30-33-11	ALL
	F	DED		W0144	71HZ			29-11-14	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0100

Page 335 End

Mar 14/2007



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0200		<b>BACT44B1948U</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>D</b>	<b>DIODEBLOCK-REF284T0189-</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>F</b>	<b>BACM15C1A</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>G</b>	<b>BACM15C1B</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>H</b>	<b>BACB15C2A</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>R</b>	<b>RESISTORBLOCK-REF284T0189-</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>X</b>	<b>BACM15C3A</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>Y</b>	<b>BACM15C3B</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>Z</b>	<b>BACM15C3C</b>					<b>P033-00/ /</b>		<b>ALL</b>
	G	19	2	W0052	053	16		33-31-41	ALL
	G	19	2	W0142	121	16		33-31-41	ALL
	G	19	2	W0142	122	18		33-31-41	ALL
	Z	22	BJ	W0144	028	24		27-58-11	ALL
	Z	22	BJ	W0144	031	24		27-58-11	ALL
	Z	22	BJ	W0144	148	24		31-31-13	ALL
	Z	22	BJ	W0144	765	24		27-58-11	ALL
	Z	22	BJ	W0144	766	24		27-58-11	ALL
	F	A001	2	W0052	001	20		24-31-11	ALL
	F	A001	2	W0142	759	20		24-31-11	ALL
	F	A002	2	W0052	003	20		24-31-11	ALL
	F	A002	2	W0142	761	20		24-31-11	ALL
	X	A003	BJ	W0142	897	24		30-31-11	ALL
	X	A003	BJ	W0144	759	24		30-31-11	ALL
	X	A004	BJ	W0142	093	24		36-11-41	ALL
	X	A004	BJ	W0144	793	24		36-11-41	ALL
	Y	A005	BJ	W0142	18G	24		73-21-14	ALL
	Y	A005	BJ	W0144	18G	24		73-21-14	ALL
	Y	A006	BJ	W0142	02P	24		30-32-11	ALL
	Y	A006	BJ	W0142	02Q	22		30-32-11	ALL
	Y	A006	BJ	W0144	538	22		30-32-11	ALL
	F	A007	2	W0142	18D	24		73-21-14	ALL
	F	A007	2	W0146	18E	24		73-21-14	ALL
	F	A008	2	W0052	022	18		38-15-11	ALL
	F	A008	2	W0142	105	18		38-15-11	ALL
	F	A009	2	W0052	024	18		38-15-11	ALL
	F	A009	2	W0142	107	18		38-15-11	ALL
	F	A010	2	W0052	030	18		30-71-11	ALL
	F	A010	2	W0142	109	18		30-71-11	ALL
	F	A012	2	W0052	039	22		33-22-41	ALL
	F	A012	2	W0142	112	22		33-22-41	ALL
	F	A013	2	W0052	042	20		33-22-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 1

Jun 28/2006



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0200		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>H</b>	<b>BACB15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>R</b>	<b>RESISTORBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	F	A013	2	W0142	114	20		33-22-11	ALL
	F	A014	2	W0052	046	24		33-21-31	ALL
	F	A014	2	W0142	116	24		33-21-31	ALL
	F	A015	2	W0052	048	18		33-31-11	ALL
	F	A015	2	W0142	118	18		33-31-11	ALL
	F	A016	2	W0052	052	22		33-24-11	050-099
	F	A016	2	W0052	052	16		33-24-11	150-199, 275-299
	F	A016	2	W0142	120	22		33-24-11	050-099
	F	A016	2	W0142	120	16		33-24-11	150-199, 275-299
	D	A017	2	W0144	01X	20		27-62-11	ALL
	D	A017	2	W0144	797	22		27-62-11	ALL
	F	A018	2	W0052	055	22		33-24-11	050-099
	F	A018	2	W0052	055	16		33-24-11	150-199, 275-299
	F	A018	2	W0142	124	22		33-24-11	050-099
	F	A018	2	W0142	124	16		33-24-11	150-199, 275-299
	R	A020	2	W0144	06M	22		27-62-11	ALL
	R	A020	2	W0144	798	22		27-62-11	ALL
	Y	A023	BJ	W0142	71B	20		29-11-14	ALL
	Y	A023	BJ	W0142	71F	20		29-11-14	ALL
	Y	A023	BJ	W0144	71K	20		29-11-14	ALL
	Y	A024	BJ	W0144	037	24		27-58-11	ALL
	Y	A024	BJ	W0144	145	24		27-58-11	ALL
	Y	A024	BJ	W0144	201B	24		31-31-13	ALL
	D	A025	2	W0142	08Q	24		29-11-22	ALL
	X	B004	BJ	W0142	094	24		36-11-41	ALL
	X	B004	BJ	W0144	794	24		36-11-41	ALL
	F	C001	2	W0052	002	20		24-31-11	ALL
	F	C001	2	W0142	760	20		24-31-11	ALL
	F	C002	2	W0052	073	22		33-24-11	ALL
	F	C002	2	W0142	09J	22		33-24-11	ALL
	X	C003	BJ	W0142	091	24		36-11-41	ALL

## TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 2

Jun 28/2006



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0200		BACT44B1948U (continued)					P033-00/ /		ALL
TB0200	D	DIODEBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0200	F	BACM15C1A (continued)					P033-00/ /		ALL
TB0200	G	BACM15C1B (continued)					P033-00/ /		ALL
TB0200	H	BACB15C2A (continued)					P033-00/ /		ALL
TB0200	R	RESISTORBLOCK-REF284T0189- (continued)					P033-00/ /		ALL
TB0200	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0200	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0200	Z	BACM15C3C (continued)					P033-00/ /		ALL
	X	C003	BJ	W0144	791	24		36-11-41	ALL
	X	C004	BJ	W0142	05G	24		21-53-22	ALL
	X	C004	BJ	W0144	06D	24		21-53-22	ALL
	Y	C005	BJ	W0142	02B	22		28-42-11	ALL
	Y	C005	BJ	W0142	02C	24		28-42-11	ALL
	Y	C005	BJ	W0142	798	22		28-42-11	ALL
	Y	C006	BJ	W0142	18GZ			73-21-14	ALL
	Y	C006	BJ	W0144	18GZ			73-21-14	ALL
	F	C007	2	W0142	18DZ			73-21-14	ALL
	F	C007	2	W0146	18EZ			73-21-14	ALL
	F	C008	2	W0052	023	18		38-15-11	ALL
	F	C008	2	W0142	106	18		38-15-11	ALL
	F	C009	2	W0052	034	20		33-31-11	ALL
	F	C009	2	W0142	108	20		33-31-11	ALL
	F	C010	2	W0052	029	20		30-71-11	ALL
	F	C010	2	W0142	110	20		30-71-11	ALL
	F	C011	2	W0052	036	24		33-21-11	ALL
	F	C011	2	W0142	111	24		33-21-11	ALL
	F	C012	2	W0052	040	20		33-22-42	ALL
	F	C012	2	W0142	113	20		33-22-42	ALL
	F	C013	2	W0052	043	20		33-27-11	ALL
	F	C013	2	W0142	115	20		33-27-11	ALL
	F	C014	2	W0052	047	24		77-35-11	ALL
	F	C014	2	W0142	117	24		77-35-11	ALL
	F	C015	2	W0052	050	22		33-22-21	ALL
	F	C015	2	W0142	125	22		33-22-21	ALL
	F	C016	2	W0052	051	22		33-24-11	050-099
	F	C016	2	W0052	051	16		33-24-11	150-199, 275-299
	F	C016	2	W0142	119	22		33-24-11	050-099
	F	C016	2	W0142	119	16		33-24-11	150-199, 275-299
	D	C017	2	W0144	799	22		27-62-11	ALL

## TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 3

Jun 28/2006



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0200		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>H</b>	<b>BACB15C2A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>R</b>	<b>RESISTORBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0200	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	F	C018	2	W0052	049	20		33-11-14	ALL
	F	C018	2	W0142	126	20		33-11-14	ALL
	R	C020	2	W0144	799	22		27-62-11	ALL
	Y	C023	BJ	W0144	036	24		27-58-11	ALL
	Y	C023	BJ	W0144	144	24		27-58-11	ALL
	Y	C023	BJ	W0144	201R	24		31-31-13	ALL
	Y	C024	BJ	W0142	70F	20		29-11-14	ALL
	Y	C024	BJ	W0142	71A	20		29-11-14	ALL
	Y	C024	BJ	W0142	71E	20		29-11-14	ALL
	D	C025	2	W0142	07T	22		29-11-22	ALL
	D	C025	2	W0144	763	22		29-11-22	ALL
	X	D003	BJ	W0142	092	24		36-11-41	ALL
	X	D003	BJ	W0144	792	24		36-11-41	ALL
	D	DED		W0142	08QZ			29-11-22	ALL
	Y	DED		W0142	71BZ			29-11-14	ALL
	Y	DED		W0142	71FZ			29-11-14	ALL
	X	DED		W0142	897Z			30-31-11	ALL
	Y	DED		W0144	538Z			30-32-11	ALL
<b>TB0201</b>		<b>284T0019</b>					<b>0139/170/R006</b>		<b>ALL</b>
<b>TB0201</b>	<b>F</b>	<b>BACM15C1A</b>					<b>0133/170/R011</b>		<b>ALL</b>
<b>TB0201</b>	<b>G</b>	<b>BACM15C1B</b>					<b>0133/170/R011</b>		<b>050-099</b>
	F	A002	2	W0779	207W	24		34-43-11	ALL
	F	A002	2	W0779	208W	24		34-43-11	ALL
	F	A003	2	W0779	209W	24		34-43-11	ALL
	F	A003	2	W0779	210W	24		34-43-11	ALL
	F	C002	2	W0779	207WB	24		34-43-11	ALL
	F	C002	2	W0779	208WB	24		34-43-11	ALL
	F	C003	2	W0779	209WB	24		34-43-11	ALL
	F	C003	2	W0779	210WB	24		34-43-11	ALL

**TERMINAL STRIP LIST**

D280T132

**91-21-41**

Section TB0200

Page 4

Jun 28/2006





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0203</b>		<b>284T0020</b>					<b>0164/140/R020</b>		<b>ALL</b>
<b>TB0203</b>	<b>F</b>	<b>BACM15C1A</b>					<b>0164/140/R020</b>		<b>ALL</b>
	F			W0803	207Z			34-43-21	ALL
	F			W0803	208Z			34-43-21	ALL
	F			W0803	209Z			34-43-21	ALL
	F			W0803	210Z			34-43-21	050-099, 151
	F			W0803	FRA			34-43-21	ALL
	F			W0803	FRB			34-43-21	ALL
	F			W0803	FRC			34-43-21	ALL
	F			W0803	FRD			34-43-21	050-099, 151
	F	A002	2	W0803	207W	24		34-43-21	ALL
	F	A002	2	W0803	208W	24		34-43-21	ALL
	F	A003	2	W0803	209W	24		34-43-21	ALL
	F	A003	2	W0803	210W	24		34-43-21	ALL
	F	C002	2	W0803	207WB	24		34-43-21	ALL
	F	C002	2	W0803	208WB	24		34-43-21	ALL
	F	C003	2	W0803	209WB	24		34-43-21	ALL
	F	C003	2	W0803	210WB	24		34-43-21	ALL
<b>TB0205</b>		<b>284T0026</b>					<b>SHELF/E01/02</b>		<b>ALL</b>
<b>TB0205</b>	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E01/02</b>		<b>ALL</b>
	G	6	2	W1103	238WB	24		34-43-11	ALL
	G	6	2	W1103	251WB	24		34-43-11	ALL
	G	6	2	W1103	252WB	24		34-43-11	ALL
	G	7	2	W1103	238W	24		34-43-11	ALL
	G	7	2	W1103	251W	24		34-43-11	ALL
	G	7	2	W1103	252W	24		34-43-11	ALL
	G	8	2	W1100	215WB	24		34-43-21	ALL
	G	8	2	W1100	218WB	24		34-43-11	ALL
	G	8	2	W1103	235WB	24		34-43-11	ALL
	G	9	2	W1100	215W	24		34-43-21	ALL
	G	9	2	W1100	218W	24		34-43-11	ALL
	G	9	2	W1103	235W	24		34-43-11	ALL
	G	REF		W1100	215Z			34-43-21	ALL
	G	REF		W1100	218Z			34-43-11	ALL
	G	REF		W1100	FRE			34-43-11	ALL
	G	REF		W1100	FRI			34-43-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 5

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0207		<b>BACT44A0580D</b>					<b>0163/204/L021</b>		<b>ALL</b>
TB0207	<b>F</b>	<b>BACM15C1A</b>					<b>0163/204/L021</b>		<b>ALL</b>
TB0207	<b>G</b>	<b>BACM15C1B</b>					<b>0163/204/L021</b>		<b>ALL</b>
	G	11	2	W0443	WBB	22		23-51-11	ALL
	G	11	2	W0443	WBV	22		23-51-11	ALL
	G	11	2	W0629	003	24		23-51-11	ALL
	F	A001	2	W0443	WKY	22		22-11-32	ALL
	F	A001	2	W0483	006	22		22-11-32	ALL
	F	A002	2	W0443	WGR	22		22-11-12	ALL
	F	A002	2	W0481	010	22		22-11-12	ALL
	F	A003	2	W0443	WBU	22		22-11-12	ALL
	F	A003	2	W0481	008	22		22-11-12	ALL
	F	A004	2	W0443	WBN	22		22-11-22	ALL
	F	A004	2	W0485	006	22		22-11-22	ALL
	F	A005	2	W0443	WOR	22		27-41-11	ALL
	F	A005	2	W1283	008	20		27-41-11	ALL
	F	A006	2	W0443	WBK	22		27-41-11	ALL
	F	A006	2	W1281	006	20		27-41-11	ALL
	F	A007	2	W0443	WRD	22		27-41-11	ALL
	F	A007	2	W1281	008	20		27-41-11	ALL
	F	A008	2	W0443	WGY	22		23-51-11	ALL
	F	A008	2	W0629	002	24		23-51-11	ALL
	F	C001	2	W0443	WBG	22		22-11-32	ALL
	F	C001	2	W0483	005	22		22-11-32	ALL
	F	C002	2	W0443	WHT	22		22-11-12	ALL
	F	C002	2	W0481	009	22		22-11-12	ALL
	F	C003	2	W0443	WYL	22		22-11-12	ALL
	F	C003	2	W0481	007	22		22-11-12	ALL
	F	C004	2	W0443	WBL	22		22-11-22	ALL
	F	C004	2	W0485	005	22		22-11-22	ALL
	F	C005	2	W0443	WVI	22		27-41-11	ALL
	F	C005	2	W1283	009	20		27-41-11	ALL
	F	C006	2	W0443	WBO	22		27-41-11	ALL
	F	C006	2	W1281	007	20		27-41-11	ALL
	F	C008	2	W0443	WBR	22		23-51-11	ALL
	F	C008	2	W0629	004	24		23-51-11	ALL
TB0209		<b>284T0384-9</b>					<b>SHELF/E01/04</b>		<b>ALL</b>
TB0209	<b>R</b>	<b>RESISTORBLOCK-REF284T0114-</b>					<b>SHELF/E01/04</b>		<b>ALL</b>
	R			W0107	259Z			34-43-21	ALL
	R			W0107	FRB			34-43-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 6

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0209		<b>284T0384-9 (continued)</b>					<b>SHELF/E01/04</b>		<b>ALL</b>
TB0209	<b>R</b>	<b>RESISTORBLOCK-REF284T0114- (continued)</b>					<b>SHELF/E01/04</b>		<b>ALL</b>
	R			W0117	258Z			34-43-21	ALL
	R			W0117	FRB			34-43-21	ALL
	R	A006	2	W0117	257W	24		34-43-11	ALL
	R	A006	2	W1127	257W	24		34-43-11	ALL
	R	A007	2	W0107	256W	24		34-43-11	ALL
	R	A007	2	W1127	256W	24		34-43-11	ALL
	R	A008	2	W0107	259W	24		34-43-21	ALL
	R	A008	2	W1127	253W	24		34-43-21	ALL
	R	A009	2	W0117	258W	24		34-43-21	ALL
	R	A009	2	W1127	252W	24		34-43-21	ALL
	R	C006	2	W0117	257WB	24		34-43-11	ALL
	R	C006	2	W1127	257WB	24		34-43-11	ALL
	R	C007	2	W0107	256WB	24		34-43-11	ALL
	R	C007	2	W1127	256WB	24		34-43-11	ALL
	R	C008	2	W0107	259WB	24		34-43-21	ALL
	R	C008	2	W1127	253WB	24		34-43-21	ALL
	R	C009	2	W0117	258WB	24		34-43-21	ALL
	R	C009	2	W1127	252WB	24		34-43-21	ALL
TB0210		<b>BACT44B0910U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>F</b>	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>G</b>	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>H</b>	<b>BACM15C2A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>X</b>	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>Z</b>	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	11	BJ	W0192	01V	20		30-71-24	050-099, 150-199
	Z	11	BJ	W0192	08S	20		30-71-24	050-099, 150-199
	Z	11	BJ	W0192	82Y	20		30-71-24	050-099
	Z	11	BJ	W0192	895	20		30-71-24	050-099, 150-199
	Z	11	BJ	W0192	909	20		30-71-24	150-199
	Z	12	BJ	W0188	012	24		21-61-21	ALL
	Z	12	BJ	W0192	04T	22		21-61-21	ALL
	Z	12	BJ	W0192	04V	22		21-61-21	ALL
	Z	12	BJ	W0192	04Z	24		21-61-21	ALL
	Z	12	BJ	W0192	05B	24		21-61-21	ALL
	Z	12	BJ	W0192	647	22		21-61-21	ALL
	G	5	2	W0058	026	16		38-13-11	150-199, 275-299
	G	5	2	W0192	735	16		38-13-11	150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 7

Jun 28/2006

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0210		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	G	6	2	W0192	08T	16		30-71-24	050-099, 150-199
	G	6	2	W1118	178	16		30-71-24	050-099, 150-199
	G	6	2	W1118	689	16		30-71-24	050-099, 150-199
	G	8	2	W0058	056	16		38-13-11	162-199
	G	8	2	W0192	08X	16		38-13-11	150-199
	G	8	2	W0192	19U	16		38-13-11	150-157
	Y	A001	BJ	W0188	014	24		21-61-21	150-199, 275-278
	Y	A001	BJ	W0192	08V	24		21-61-21	150-199, 275-278
	Y	A001	BJ	W0192	54V	20		30-71-24	050-099
	Y	A001	BJ	W0192	568	24		21-61-21	150-199, 275-278
	Y	A001	BJ	W0192	83B	20		30-71-24	050-099
	Y	A001	BJ	W1118	08B	20		30-71-24	050-099
	Y	A001	BJ	W1118	189	20		30-71-24	050-099
	Y	A003	BJ	W0058	080	20		21-66-21	050
	X	A003	BJ	W0058	086	22		21-66-41	051-099, 150, 152-199
	Y	A003	BJ	W0192	74E	20		21-66-21	050
	X	A003	BJ	W0192	76G	22		21-66-41	051-099, 150, 152-199
	Y	A004	BJ	W0192	01Y	20		30-71-24	050, 150-154
	Y	A004	BJ	W0192	54X	20		30-71-24	050
	Y	A004	BJ	W0192	59N	20		30-71-24	050
	Y	A004	BJ	W1118	092	20		30-71-24	150-154
	Y	A004	BJ	W1118	094	20		30-71-24	150-154
	Y	A016	BJ	W0192	01D	22		31-31-11	ALL
	Y	A016	BJ	W0192	103	24		31-31-11	ALL
	Y	A016	BJ	W0198	132	22		31-31-11	ALL
	X	A017	BJ	W0192	273R	20		32-45-12	050-099, 150-199
	X	A017	BJ	W0198	207R	20		32-45-12	050-099, 150-199
	X	A019	BJ	W0198	570	22		25-33-11	050-099, 153-199, 277-299
	X	A019	BJ	W0198	570	22		21-58-16	150-152, 275-276
	X	A019	BJ	W1118	524	22		25-33-11	050-099, 153-199, 277-299
	X	A019	BJ	W1118	524	22		21-58-16	150-152, 275-276
	X	A020	BJ	W0188	11A	24		21-43-11	ALL
	X	A020	BJ	W1118	12H	24		21-43-11	ALL

**TERMINAL STRIP LIST**

D280T132

**91-21-41**

Section TB0200

Page 8

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0210		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	B017	BJ	W0192	273B	20		32-45-12	050-099, 150-199
	X	B017	BJ	W0198	207B	20		32-45-12	050-099, 150-199
	X	B019	BJ	W0192	523	24		21-58-16	ALL
	X	B019	BJ	W0198	571	24		21-58-16	ALL
	X	B020	BJ	W0188	11B	24		21-43-11	ALL
	X	B020	BJ	W1118	12G	24		21-43-11	ALL
	Y	C001	BJ	W0192	08K	22		27-81-11	ALL
	Y	C001	BJ	W1118	167	24		27-81-11	ALL
	Y	C001	BJ	W1118	179	22		27-81-21	ALL
	Y	C003	BJ	W0058	086	22		21-66-41	050
	Y	C003	BJ	W0192	76G	22		21-66-41	050
	F	C008	2	W0058	026	16		38-13-11	050-099
	F	C008	2	W0192	735	16		38-13-11	050-099
	X	C010	BJ	W0192	910	20		30-71-24	150-199
	X	C010	BJ	W1118	095	20		30-71-24	150-199
	Y	C015	BJ	W0192	01U	24		21-25-21	ALL
	Y	C015	BJ	W0192	01X	24		21-25-21	ALL
	Y	C015	BJ	W0192	151	22		21-25-21	ALL
	Y	C016	BJ	W0192	102	24		31-31-11	ALL
	Y	C016	BJ	W0192	122	22		31-31-11	ALL
	Y	C016	BJ	W0198	133	22		31-31-11	ALL
	X	C017	BJ	W0192	273Z			32-45-12	050-099, 150-199
	X	C017	BJ	W0198	207Z			32-45-12	050-099, 150-199
	X	C019	BJ	W0188	006	24		21-58-16	ALL
	X	C019	BJ	W0192	522	24		21-58-16	ALL
	X	C020	BJ	W0188	11C	24		21-43-11	ALL
	X	C020	BJ	W1118	12F	24		21-43-11	ALL
	X	D003	BJ	W0058	080	20		21-66-21	051-099, 162-199
	X	D003	BJ	W0192	74E	20		21-66-21	051-099, 162-199
	X	D009	BJ	W0188	049	22		28-42-13	050-099, 155-199, 276-299
	X	D009	BJ	W0198	549	22		28-42-13	050-099, 155-199, 276-299
	X	D019	BJ	W0192	14M	22		31-31-11	ALL
	X	D019	BJ	W0198	199	22		31-31-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 9

Jun 28/2006



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0210		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	F	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	G	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	H	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0210	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	D020	BJ	W0192	51H	20		38-32-11	050-099, 155-199, 277-299
	X	D020	BJ	W0192	51H	20		SPARE	276
	X	D020	BJ	W1118	150	20		38-32-11	050-099, 155-199, 277-299
	X	D020	BJ	W1118	150	20		SPARE	276
	X	DED		W0188	049Z			28-42-13	050-099, 155-199, 276-299
	X	DED		W0198	549Z			28-42-13	050-099, 155-199, 276-299
TB0211		<b>284T0026</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
TB0211	G	<b>BACM15C1B</b>					<b>SHELF/E01/05</b>		<b>ALL</b>
	G	1	2	W0109	235WB	24		34-43-21	ALL
	G	1	2	W1119	235WB	24		34-43-21	ALL
	G	2	2	W1119	235W	24		34-43-21	ALL
	G	3	2	W0119	502WB	24		34-43-21	050-099, 150-199, 275-278
	G	3	2	W1119	238WB	24		34-43-21	ALL
	G	4	2	W1119	238W	24		34-43-21	ALL
	G	6	2	W0109	238WB	24		34-43-11	050-099, 151
	G	6	2	W0109	911WB	24		34-46-13	150, 152-199, 275-299
	G	7	2	W0109	235W	24		34-43-21	ALL
	G	7	2	W0109	238W	24		34-43-11	050-099, 151
	G	7	2	W0109	911W	24		34-46-13	150, 152-199, 275-299
	G	8	2	W0109	913WB	24		34-46-13	150, 152-199, 275-299
	G	8	2	W0119	502WB	24		34-43-21	280-299
	G	8	2	W0119	503WB	24		34-43-21	050-099, 151
	G	9	2	W0109	913W	24		34-46-13	150, 152-199, 275-299
	G	9	2	W0119	502W	24		34-43-21	ALL
	G	9	2	W0119	503W	24		34-43-21	050-099, 151
	G	DED		W0109	911Z			34-46-13	150, 152-199, 275-299
	G	DED		W0109	913Z			34-46-13	150, 152-199, 275-299
	G	REF		W0109	235Z			34-43-21	ALL
	G	REF		W0109	238Z			34-43-11	050-099, 151
	G	REF		W0109	FRA			34-43-21	ALL
	G	REF		W0109	FRB			34-43-11	050-099, 151

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 10

Jun 28/2006



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0212		<b>BACT44B0910U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	F	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	G	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	H	<b>BACM15C2A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	X	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	Y	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	Z	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	15	BJ	W0192	05F	22		21-61-31	ALL
	Z	15	BJ	W0192	05H	22		21-61-31	ALL
	Z	15	BJ	W0192	05N	24		21-61-31	ALL
	Z	15	BJ	W0192	05P	24		21-61-31	ALL
	Z	15	BJ	W0192	882	22		21-61-31	ALL
	Z	16	BJ	W0192	18E	24		73-21-11	ALL
	Z	16	BJ	W0198	125	24		76-11-11	ALL
	Z	16	BJ	W0198	134	20		76-11-11	ALL
	Z	16	BJ	W0198	137	20		76-11-11	ALL
	Z	16	BJ	W0198	148	20		76-11-11	050-099, 150-154, 275-276
	Z	16	BJ	W0198	148	24		76-11-11	155-199, 277-299
	Z	16	BJ	W0198	604	24		76-11-11	ALL
	Z	17	BJ	W0192	004	24		28-22-12	ALL
	Z	17	BJ	W0192	63E	24		28-22-12	050-099, 155-199, 276-299
	Z	17	BJ	W0192	78U	24		28-22-12	ALL
	Z	17	BJ	W0192	79J	24		28-22-12	ALL
	Z	17	BJ	W0192	79X	24		28-22-12	ALL
	Z	18	BJ	W0192	121	22		49-61-11	ALL
	Z	18	BJ	W0198	005	22		49-61-11	ALL
	Z	18	BJ	W0198	006	22		49-61-11	ALL
	Z	18	BJ	W0198	155	22		49-61-11	ALL
	Z	19	BJ	W0188	073	24		28-42-12	ALL
	Z	19	BJ	W0188	074	22		28-42-12	ALL
	Z	19	BJ	W0188	075	22		28-42-12	ALL
	Z	19	BJ	W0192	63C	22		28-42-12	050-099, 155-199, 276-299
	Z	19	BJ	W0192	79V	24		28-42-12	ALL
	Z	20	BJ	W0192	50G	22		49-61-11	050-099, 162-199, 275-299
	Z	20	BJ	W0198	013	22		49-61-11	ALL
	Z	20	BJ	W0198	021	22		49-61-11	ALL
	Z	20	BJ	W0198	022	22		49-61-11	ALL
	X	A001	BJ	W0058	046	20		30-71-23	275
	X	A001	BJ	W1118	148	20		30-71-23	275
	X	A002	BJ	W0192	650	22		49-61-11	ALL
	X	A002	BJ	W0198	018	22		49-61-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 11

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0212		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	F	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	G	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	H	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	A003	BJ	W0192	263R	24		28-41-11	ALL
	X	A003	BJ	W0198	202R	24		28-41-11	ALL
	Y	A005	BJ	W0198	012	22		49-61-11	ALL
	Y	A005	BJ	W0198	019	22		49-61-11	ALL
	Y	A005	BJ	W0198	502	24		49-61-11	ALL
	Y	A007	BJ	W0192	79B	24		28-42-12	ALL
	Y	A007	BJ	W0192	79G	24		28-42-12	ALL
	Y	A007	BJ	W0198	02A	24		28-22-12	150-199
	Y	A007	BJ	W1118	14A	24		28-22-12	050-099, 275-299
	Y	A008	BJ	W0198	106	22		28-25-21	ALL
	Y	A008	BJ	W0198	515	24		28-25-21	ALL
	Y	A008	BJ	W0198	553	24		28-25-21	ALL
	Y	A010	BJ	W0188	130	24		27-51-61	ALL
	Y	A010	BJ	W0188	133	24		27-51-61	050-099
	Y	A010	BJ	W0192	12X	24		27-51-61	ALL
	Y	A011	BJ	W0192	65J	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	A011	BJ	W0192	65Q	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	A011	BJ	W0192	682	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	A012	BJ	W0192	502	24		21-58-15	ALL
	Y	A012	BJ	W0192	890	24		21-58-15	ALL
	Y	A012	BJ	W0192	89A	24		21-58-15	ALL
	Y	A013	BJ	W0192	21F	24		77-35-11	ALL
	Y	A013	BJ	W0192	21G	24		77-35-11	ALL
	Y	A013	BJ	W0192	608	24		77-35-11	ALL
	Y	A014	BJ	W0188	043	22		28-31-12	051-099, 155-199, 277-299
	Y	A014	BJ	W0192	66W	22		28-31-12	051-099, 162-164
	Y	A014	BJ	W0192	66X	22		28-31-12	051-099, 155-199, 277-299
	X	B001	BJ	W0058	047	20		30-71-23	275
	X	B001	BJ	W1118	149	20		30-71-23	275
	X	B002	BJ	W0192	50F	22		49-61-11	050-099, 162-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 12

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0212		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	B002	BJ	W0198	50B	22		49-61-11	050-099, 162-199, 275-299
	X	B003	BJ	W0192	263B	24		28-41-11	ALL
	X	B003	BJ	W0198	202B	24		28-41-11	ALL
	X	C001	BJ	W0058	057	20		30-71-23	275
	X	C001	BJ	W1118	188	20		30-71-23	275
	Y	C005	BJ	W0198	500	20		25-33-11	050-099, 155-199, 277-299
	Y	C005	BJ	W1118	106	20		25-33-11	155-199, 277-299
	Y	C005	BJ	W1118	517	20		25-33-11	050-099
	Y	C006	BJ	W0192	78T	24		28-22-12	150-154, 275
	Y	C006	BJ	W0192	79H	24		28-22-12	150-154, 275
	Y	C006	BJ	W0198	189	24		28-22-12	150-154, 275
	Y	C008	BJ	W0192	03S	24		21-58-11	ALL
	Y	C008	BJ	W0192	03T	24		21-58-11	ALL
	Y	C008	BJ	W0192	511	24		21-58-11	ALL
	Y	C009	BJ	W0192	13E	22		27-81-11	ALL
	Y	C009	BJ	W1118	514	22		27-81-11	ALL
	Y	C009	BJ	W1118	515	22		27-81-21	ALL
	Y	C010	BJ	W0192	07U	24		29-11-12	ALL
	Y	C010	BJ	W0192	126	22		29-11-12	ALL
	Y	C010	BJ	W0192	546	22		29-11-12	ALL
	Y	C010	BJ	W0192	836	24		29-11-12	ALL
	Y	C012	BJ	W0192	061	24		36-11-62	150-154, 275
	Y	C012	BJ	W0192	65U	24		36-11-62	150-154, 275
	Y	C012	BJ	W0192	65Y	24		36-11-62	150-154, 275
	Y	CAP	Y	W0192	66W	22		28-31-12	155-157, 165-199, 277-299
	Y	DED		W0188	043Z			28-31-12	051-099, 155-199, 277-299
	Z	DED		W0188	074Z			28-42-12	ALL
	Y	DED		W0192	03SZ			21-58-11	ALL
	Y	DED		W0192	126Z			29-11-12	ALL
	Y	DED		W0192	511Z			21-58-11	ALL
	Y	DED		W0192	546Z			29-11-12	ALL
	Z	DED		W0192	63CZ			28-42-12	050-099, 155-199, 276-299
	Y	DED		W0192	66WZ			28-31-12	051-099, 155-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 13

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0212		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	F	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	G	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	H	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0212	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	DED		W0192	66XZ			28-31-12	051-099, 155-199, 277-299
	Y	DED		W0198	02AZ			28-22-12	150-199
	Z	DED		W0198	604Z			76-11-11	ALL
TB0214	Z	<b>BACM15C3C</b>					<b>P001-00/ /</b>		<b>ALL</b>
TB0215		<b>BACT44A0700U</b>					<b>0200/205/L006</b>		<b>ALL</b>
TB0215	F	<b>BACM15C1A</b>					<b>0200/205/L006</b>		<b>ALL</b>
TB0215	G	<b>BACM15C1B</b>					<b>0200/205/L006</b>		<b>ALL</b>
	G	11	2	W5150	377	22		22-12-21	ALL
	G	11	2	W5150	380	22		22-12-21	ALL
	G	13	2	W5150	383	22		22-12-31	ALL
	G	13	2	W5150	386	22		22-12-31	ALL
	G	15	2	W5150	360	22		27-62-11	ALL
	G	15	2	W5150	361	22		27-62-11	ALL
	G	15	2	W5150	B-A			27-62-11	ALL
	G	3	2	W5150	417	22		27-51-31	ALL
	G	3	2	W5150	C-E			27-51-31	ALL
	G	6	2	W5150	422	22		27-58-31	ALL
	G	6	2	W5150	D-E			27-58-31	ALL
	F	A001	2	W5150	413	22		27-51-31	ALL
	F	A001	2	W5150	C-A			27-51-31	ALL
	F	A002	2	W5150	415	22		27-51-31	ALL
	F	A002	2	W5150	C-C			27-51-31	ALL
	F	A004	2	W5150	418	22		27-58-31	ALL
	F	A004	2	W5150	D-A			27-58-31	ALL
	F	A005	2	W5150	420	22		27-58-31	ALL
	F	A005	2	W5150	D-C			27-58-31	ALL
	F	A008	2	W5150	365	22		22-12-11	ALL
	F	A008	2	W5150	367	22		22-12-11	ALL
	F	A009	2	W5150	370	22		22-32-13	ALL
	F	A009	2	W5150	372	22		22-32-13	ALL
	F	A014	2	W5150	426	22		27-62-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 14

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0215		<b>BACT44A0700U (continued)</b>					<b>0200/205/L006</b>		<b>ALL</b>
TB0215	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>0200/205/L006</b>		<b>ALL</b>
TB0215	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>0200/205/L006</b>		<b>ALL</b>
	F	A014	2	W5150	B-B			27-62-11	ALL
	F	C001	2	W5150	414	22		27-51-31	ALL
	F	C001	2	W5150	C-B			27-51-31	ALL
	F	C002	2	W5150	416	22		27-51-31	ALL
	F	C002	2	W5150	C-D			27-51-31	ALL
	F	C004	2	W5150	419	22		27-58-31	ALL
	F	C004	2	W5150	D-B			27-58-31	ALL
	F	C005	2	W5150	421	22		27-58-31	ALL
	F	C005	2	W5150	D-D			27-58-31	ALL
	F	C008	2	W5150	368	22		22-32-13	ALL
	F	C008	2	W5150	369	22		22-32-13	ALL
	F	C009	2	W5150	371	22		22-32-13	ALL
	F	C009	2	W5150	373	22		22-32-13	ALL
	F	C014	2	W5150	427	22		27-62-11	ALL
	F	C014	2	W5150	B-C			27-62-11	ALL
	F	C017	2	W5150	429	22		31-31-15	150-154
	F	C017	2	W5150	V-A			31-31-15	150-154
TB0216		<b>BACT44B0910U</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	<b>F</b>	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	<b>G</b>	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	<b>H</b>	<b>BACM15C2A</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	<b>X</b>	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	<b>Y</b>	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	<b>Z</b>	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	13	BJ	W0176	014	24		32-09-11	ALL
	Z	13	BJ	W0176	016	24		32-09-11	ALL
	Z	13	BJ	W0176	122	24		32-09-11	ALL
	Z	13	BJ	W0176	135	24		32-09-11	ALL
	Z	13	BJ	W0176	51W	24		32-09-11	ALL
	Z	13	BJ	W0176	528	24		32-09-11	ALL
	Z	13	BJ	W0176	674	24		32-09-11	ALL
	Z	13	BJ	W0184	034	24		32-09-11	ALL
	Z	14	BJ	W0176	02H	22		28-22-12	162-199, 280-299
	Z	14	BJ	W0176	11E	24		73-21-11	050-099, 150-154, 275-276
	Z	14	BJ	W0176	53E	24		28-22-12	162-199, 280-299
	Z	14	BJ	W0176	75W	22		28-22-12	162-199, 280-299
	Z	14	BJ	W0176	83V	24		28-22-12	162-199, 280-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 15

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0216		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	14	BJ	W0176	85W	24		28-22-12	162-199, 280-299
	Z	14	BJ	W0184	01P	24		76-11-11	050-099, 150-154, 275-276
	Z	14	BJ	W0184	171	20		76-11-11	050-099, 150-154, 275-276
	Z	14	BJ	W0184	172	20		76-11-11	050-099, 150-154, 275-276
	Z	14	BJ	W0184	175	24		76-11-11	050-099, 150-154, 275-276
	Z	14	BJ	W0184	182	20		76-11-11	050-099, 150-154, 275-276
	Z	19	BJ	W0176	02H	22		28-22-12	050-099, 150-157, 275-278
	Z	19	BJ	W0176	53E	24		28-22-12	050-099, 155-157, 276-278
	Z	19	BJ	W0176	75W	22		28-22-12	050-099, 150-157, 275-278
	Z	19	BJ	W0176	83V	24		28-22-12	050-099, 150-157, 275-278
	Z	19	BJ	W0176	85W	24		28-22-12	050-099, 150-157, 275-278
	Y	A002	BJ	W0176	847	24		29-11-32	ALL
	Y	A002	BJ	W0184	668	24		29-11-32	ALL
	X	A003	BJ	W0176	07J	20		27-32-31	ALL
	X	A003	BJ	W0180	122	20		27-32-31	ALL
	X	A004	BJ	W0176	81C	24		30-21-11	050-099, 150-199
	X	A004	BJ	W0180	139	24		30-21-11	050-099, 150-199
	Y	A005	BJ	W0176	04Y	24		24-51-71	ALL
	Y	A005	BJ	W0180	118	24		24-51-71	ALL
	Y	A005	BJ	W0180	124	24		24-51-71	ALL
	Y	A006	BJ	W0176	023	24		76-11-11	ALL
	Y	A006	BJ	W0184	174	20		76-11-11	ALL
	Y	A006	BJ	W0184	176	20		76-11-11	ALL
	F	A007	2	W0176	794	18		28-41-12	ALL
	F	A007	2	W0180	054	18		28-41-12	ALL
	F	A008	2	W0056	051	18		21-24-11	050-099, 150-199
	F	A008	2	W0184	858	18		21-24-11	050-099, 150-199
	Y	A011	BJ	W0176	853	24		24-22-11	ALL
	Y	A011	BJ	W0176	866	24		24-22-11	ALL
	Y	A011	BJ	W0176	868	24		24-22-11	ALL
	Y	A016	BJ	W0176	634	22		21-58-16	ALL
	Y	A016	BJ	W0184	067	22		21-58-16	ALL
	Y	A016	BJ	W0184	087	22		21-58-16	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 16

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0216		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	A018	BJ	W0176	532	24		36-21-11	050-099, 156-162, 166-199, 277-299
	Y	A018	BJ	W0176	65F	24		36-21-11	050-099, 156-162, 166-199, 277-299
	Y	A018	BJ	W0176	67F	24		36-21-11	050-099, 156-162, 166-199, 277-299
	Y	C001	BJ	W0176	692	24		73-21-17	ALL
	Y	C001	BJ	W0184	652	24		29-11-32	ALL
	Y	C001	BJ	W0184	674	24		29-11-32	ALL
	Y	C002	BJ	W0176	04R	24		24-51-71	ALL
	Y	C002	BJ	W0176	05B	24		24-51-71	ALL
	Y	C002	BJ	W0180	116	24		24-51-71	ALL
	X	C003	BJ	W0176	621	24		23-31-13	ALL
	X	C003	BJ	W0184	614	24		23-31-13	ALL
	Y	C005	BJ	W0176	62R	24		21-43-11	050-099, 150-199
	Y	C005	BJ	W0180	128	24		21-44-21	050-099, 150-199
	Y	C005	BJ	W0182	106	24		21-44-21	050-099, 150-199
	F	C007	2	W0056	050	18		21-24-11	050-099, 150-199
	F	C007	2	W0184	711	18		21-24-11	050-099, 150-199
	F	C008	2	W0056	052	18		21-24-11	050-099, 150-199
	F	C008	2	W0184	859	18		21-24-11	050-099, 150-199
	Y	C009	BJ	W0184	646	22		29-11-32	ALL
	Y	C009	BJ	W0184	818	24		29-11-32	ALL
	Y	C009	BJ	W0184	819	22		29-11-32	ALL
	Y	C010	BJ	W0176	53G	24		28-22-12	050-099, 155-199, 276-299
	Y	C010	BJ	W0176	697	20		28-22-12	ALL
	Y	C010	BJ	W0176	83U	24		28-22-12	ALL
	Y	C010	BJ	W0184	765	24		28-22-12	ALL
	Y	C011	BJ	W0176	01J	24		21-51-11	ALL
	Y	C011	BJ	W0176	01K	24		21-51-11	ALL
	Y	C011	BJ	W0176	01L	24		21-51-11	ALL
	Y	C012	BJ	W0176	09K	24		21-45-21	150-199, 275-299
	Y	C012	BJ	W0176	21D	24		21-45-24	150-157, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 17

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0216		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0216	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	C012	BJ	W0176	30B	24		21-45-21	275-299
	Y	C012	BJ	W0176	54P	24		21-45-21	150-199, 275-299
	Y	C018	BJ	W0184	743	22		29-11-32	ALL
	Y	C018	BJ	W0184	744	22		29-11-32	ALL
	Y	C018	BJ	W0184	777	22		29-11-32	ALL
	X	D003	BJ	W0176	833	24		23-31-13	ALL
	X	D003	BJ	W0184	615	24		23-31-13	ALL
	Z	DED		W0176	014Z			32-09-11	ALL
	Z	DED		W0176	016Z			32-09-11	ALL
	Z	DED		W0176	122Z			32-09-11	ALL
	Z	DED		W0176	135Z			32-09-11	ALL
	Z	DED		W0176	51WZ			32-09-11	ALL
	Z	DED		W0176	528Z			32-09-11	ALL
	Z	DED		W0176	674Z			32-09-11	ALL
	Y	DED		W0176	697Z			28-22-12	ALL
	F	DED		W0176	794Z			28-41-12	ALL
	Y	DED		W0176	847Z			29-11-32	ALL
	X	DED		W0180	122Z			27-32-31	ALL
	Z	DED		W0184	01PZ			76-11-11	050-099, 150-154, 275-276
	Z	DED		W0184	034Z			32-09-11	ALL
	Y	DED		W0184	765Z			28-22-12	ALL
TB0217		<b>BACT44A0400U</b>					<b>0200/205/L006</b>		<b>ALL</b>
TB0217	G	<b>BACM15C1B</b>					<b>P010-00/ /</b>		<b>ALL</b>
TB0217	H	<b>BACM15C2A</b>					<b>0200/205/L006</b>		<b>ALL</b>
	G	1	2	W5150	374	22		27-41-11	150-154
	G	1	2	W5150	E-A			27-41-11	150-154
	G	2	2	W5150	390	20		33-13-18	ALL
	G	2	2	W5150	F-A			33-13-18	ALL
	G	3	2	W5150	392	20		33-13-18	ALL
	G	3	2	W5150	K-A			33-13-18	ALL
	H	4	2	W5150	024	20		33-13-18	050-099, 155, 162-165, 275-276
	H	4	2	W5150	229R	20		33-13-18	156-157, 166-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 18

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0217		<b>BACT44A0400U (continued)</b>					<b>0200/205/L006</b>		<b>ALL</b>
TB0217	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P010-00/ /</b>		<b>ALL</b>
TB0217	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>0200/205/L006</b>		<b>ALL</b>
	H	4	2	W5150	230R	20		33-13-18	156-157, 166-199, 277-299
	H	4	2	W5150	391	20		33-13-18	050-099, 150-155, 162-165, 275-276
	H	4	2	W5150	G-A			33-13-18	ALL
	H	4	2	W5150	H-A			33-13-18	ALL
	H	9	2	W5150	229B	20		33-13-18	156-157, 166-199, 277-299
	H	9	2	W5150	230B	20		33-13-18	156-157, 166-199, 277-299
	H	9	2	W5150	G-B			33-13-18	156-157, 166-199, 277-299
	H	9	2	W5150	H-B			33-13-18	156-157, 166-199, 277-299
<b>TB0218</b>		<b>BACT44B0910U</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0218</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0218</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0218</b>	<b>H</b>	<b>BACM15C2A</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
<b>TB0218</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0218</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0218</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
	G	19	2	W0176	793	18		28-41-12	ALL
	G	19	2	W0184	596	18		28-41-12	ALL
	G	19	2	W0184	598	18		28-41-12	ALL
	X	A002	BJ	W0176	174	24		36-23-21	ALL
	X	A002	BJ	W0180	026	24		36-23-21	ALL
	X	A004	BJ	W0176	11KZ			73-21-11	275-276
	X	A004	BJ	W0176	11PZ			73-21-11	275-276
	Y	A005	BJ	W0176	53C	22		28-42-12	050-099, 155-199, 276-299
	Y	A005	BJ	W0176	85J	24		28-42-12	ALL
	Y	A005	BJ	W0184	10D	22		28-42-12	050-099, 155-199, 276-299
	Y	A005	BJ	W0184	16A	22		28-42-12	150-154, 275
	Y	A006	BJ	W0176	04F	24		32-09-11	ALL
	Y	A006	BJ	W0176	04G	24		32-09-11	ALL
	Y	A006	BJ	W0176	119	24		32-09-11	ALL
	Y	A008	BJ	W0176	05D	24		24-51-71	ALL
	Y	A008	BJ	W0180	123	24		24-51-71	ALL
	Y	A008	BJ	W0180	125	24		24-51-71	ALL
	Y	A008	BJ	W0180	127	24		24-51-71	ALL
	Y	A010	BJ	W0176	057	24		21-58-14	ALL
	Y	A010	BJ	W0176	504	24		21-58-14	ALL
	Y	A010	BJ	W0184	058	24		21-58-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 19

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0218		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0218	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
	X	A011	BJ	W0176	160	22		31-31-11	ALL
	X	A011	BJ	W0184	002	22		31-31-11	ALL
	X	A012	BJ	W0176	09E	22		31-31-11	ALL
	X	A012	BJ	W0184	857	22		31-31-11	ALL
	Y	A013	BJ	W0176	51K	24		21-58-12	ALL
	Y	A013	BJ	W0184	025	24		21-58-12	ALL
	Y	A013	BJ	W0184	588	24		21-58-12	ALL
	Y	A013	BJ	W0184	879	24		21-58-12	ALL
	Y	A014	BJ	W0176	846	24		21-24-11	050-099, 150-199
	Y	A014	BJ	W0176	855	24		21-24-11	050-099, 150-199
	Y	A014	BJ	W0184	855	24		21-24-11	050-099, 150-199
	Y	A017	BJ	W0176	11M	24		73-21-11	050-099, 150-199, 277-299
	Y	A017	BJ	W0184	216	24		73-21-11	050-099, 150-199, 277-299
	Y	A018	BJ	W0184	104	24		28-41-11	ALL
	Y	A018	BJ	W0184	205R	24		28-41-11	ALL
	Y	A018	BJ	W0184	207R	24		28-41-11	ALL
	F	A020	2	W0180	146	18		38-32-11	275-276
	F	A020	2	W0182	174	18		38-32-11	275-276
	X	B001	BJ	W0180	128	24		21-44-21	275-299
	X	B001	BJ	W0182	106	24		21-44-21	275-299
	X	B004	BJ	W0176	11K	24		73-21-11	275-276
	X	B004	BJ	W0176	11P	24		73-21-11	275-276
	X	B011	BJ	W0176	156	22		31-31-11	ALL
	X	B011	BJ	W0184	006	22		31-31-11	ALL
	X	B012	BJ	W0176	02F	24		28-22-12	150-199
	X	B012	BJ	W0184	02K	24		28-22-12	150-199
	X	C001	BJ	W0176	217B	24		21-61-51	ALL
	X	C001	BJ	W0180	201B	24		21-61-51	ALL
	X	C002	BJ	W0176	850	22		23-71-11	ALL
	X	C002	BJ	W0184	728	22		23-71-11	ALL
	X	C004	BJ	W0176	11M	24		73-21-11	275-276
	X	C004	BJ	W0184	216	24		73-21-11	275-276
	Y	C005	BJ	W0176	85U	24		28-42-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 20

Aug 05/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0218		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0218	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
	Y	C005	BJ	W0176	85V	24		28-42-12	ALL
	Y	C005	BJ	W0184	768	24		28-22-12	ALL
	Y	C006	BJ	W0184	075	20		32-44-11	ALL
	Y	C006	BJ	W0184	081	22		32-44-11	ALL
	Y	C006	BJ	W0184	808	24		32-44-11	ALL
	Y	C006	BJ	W0184	809	22		32-44-11	ALL
	Y	C007	BJ	W0176	08E	22		73-21-19	ALL
	Y	C007	BJ	W0176	683	22		73-21-19	ALL
	Y	C007	BJ	W0176	85P	22		73-21-19	050-099, 150-199
	Y	C007	%	W0184	08B	22		73-21-19	275-299
	Y	C008	BJ	W0176	51P	24		32-09-11	ALL
	Y	C008	BJ	W0176	51U	24		32-09-11	ALL
	Y	C008	BJ	W0176	51W	24		32-09-11	ALL
	Y	C009	BJ	W0176	53B	22		28-42-13	050-099, 155-199, 276-299
	Y	C009	BJ	W0176	53K	22		28-42-13	050-099, 155-199, 276-299
	Y	C009	BJ	W0184	10E	22		28-42-13	050-099, 155-199, 276-299
	X	C012	BJ	W0176	856	24		21-24-11	050-099, 150-199
	X	C012	BJ	W0184	856	24		21-24-11	050-099, 150-199
	Y	C013	BJ	W0176	45F	22		36-11-61	ALL
	Y	C013	BJ	W0176	49F	22		36-11-61	ALL
	Y	C013	BJ	W0176	72D	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Y	C013	BJ	W0176	804	22		36-11-61	050-099, 150-155, 157-165, 167-199, 275-299
	Y	C017	BJ	W0176	11G	24		73-21-11	050-099, 150-199, 277-299
	Y	C017	BJ	W0184	217	24		73-21-11	050-099, 150-199, 277-299
	Y	C018	BJ	W0184	054	24		21-58-12	ALL
	Y	C018	BJ	W0184	585	24		21-58-12	ALL
	Y	C018	BJ	W0184	75N	24		21-58-12	ALL
	F	C020	2	W0184	205B	24		28-41-11	ALL
	F	C020	2	W0184	207B	24		28-41-11	ALL
	Y	C13	BJ	W0176	804	22		36-11-61	156, 166
	X	D001	BJ	W0176	217R	24		21-61-51	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 21

Aug 05/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0218		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0218	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0218	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
	X	D001	BJ	W0180	201R	24		21-61-51	ALL
	X	D002	BJ	W0176	619	22		23-71-11	ALL
	X	D002	BJ	W0184	607	22		23-71-11	ALL
	X	D004	BJ	W0176	11G	24		73-21-11	275-276
	X	D004	BJ	W0184	217	24		73-21-11	275-276
	Y	DED		W0176	51PZ			32-09-11	ALL
	Y	DED		W0176	51UZ			32-09-11	ALL
	Y	DED		W0176	51WZ			32-09-11	ALL
	Y	DED		W0176	53BZ			28-42-13	050-099, 155-199, 276-299
	Y	DED		W0176	53CZ			28-42-12	050-099, 155-199, 276-299
	Y	DED		W0176	53KZ			28-42-13	050-099, 155-199, 276-299
	X	DED		W0184	02KZ			28-22-12	150-199
	Y	DED		W0184	058Z			21-58-14	ALL
	Y	DED		W0184	10DZ			28-42-12	050-099, 155-199, 276-299
	Y	DED		W0184	10EZ			28-42-13	050-099, 155-199, 276-299
	Y	DED		W0184	16AZ			28-42-12	150-154, 275
	Y	DED		W0184	768Z			28-22-12	ALL
TB0219		<b>BACT44A0600U</b>					<b>P010-00/ /</b>		<b>ALL</b>
TB0219	F	<b>BACM15C1A</b>					<b>P010-00/ /</b>		<b>ALL</b>
TB0219	G	<b>BACM15C1B</b>					<b>P010-00/ /</b>		<b>ALL</b>
TB0219	H	<b>BACM15C2A</b>					<b>P010-00/ /</b>		<b>ALL</b>
	G	2	2	W5150	389	22		33-16-18	ALL
	G	2	2	W5150	425	22		33-16-18	ALL
	G	5	2	W5150	426	22		27-62-11	ALL
	G	5	2	W5150	A-D			27-62-11	ALL
	G	6	2	W5150	359	22		27-62-11	ALL
	G	6	2	W5150	427	22		27-62-11	ALL
	G	6	2	W5150	A-F			27-62-11	ALL
	G	8	2	W5150	409	22		32-42-12	ALL
	G	8	2	W5150	L-B			32-42-12	ALL
	H	9	2	W5150	401	22		32-42-12	ALL
	H	9	2	W5150	402	22		32-42-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 22

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0219		<b>BACT44A0600U (continued)</b>					<b>P010-00/ /</b>		<b>ALL</b>
TB0219	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P010-00/ /</b>		<b>ALL</b>
TB0219	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P010-00/ /</b>		<b>ALL</b>
TB0219	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P010-00/ /</b>		<b>ALL</b>
	H	9	2	W5150	406	22		32-42-12	ALL
	H	9	2	W5150	L-A			32-42-12	ALL
	F	A001	2	W5150	387	22		32-44-11	ALL
	F	A001	2	W5150	423	22		32-44-11	ALL
	F	A003	2	W5150	355	22		27-62-11	ALL
	F	A003	2	W5150	A-A			27-62-11	ALL
	F	A004	2	W5150	357	22		27-62-11	ALL
	F	A004	2	W5150	A-C			27-62-11	ALL
	F	A007	2	W5150	412	22		31-51-41	ALL
	F	A007	2	W5150	L-E			31-51-41	ALL
	F	C001	2	W5150	388	22		33-16-18	ALL
	F	C001	2	W5150	424	22		33-16-18	ALL
	F	C003	2	W5150	356	22		27-62-11	ALL
	F	C003	2	W5150	A-B			27-62-11	ALL
	F	C004	2	W5150	358	22		27-62-11	ALL
	F	C004	2	W5150	A-E			27-62-11	ALL
	F	C007	2	W5150	428	22		29-11-32	ALL
	F	C007	2	W5150	L-F			29-11-32	ALL
		CAP	Y	W5150	L-C			32-42-12	ALL
<b>TB0220</b>		<b>BACT44B0910U</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0220</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0220</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0220</b>	<b>H</b>	<b>BACM15C2A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0220</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0220</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0220</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
	Y			W0176	03TZ			78-34-11	ALL
	Y			W0176	22WZ			78-34-11	ALL
	Y	A001	BJ	W0176	19H	24		73-21-18	050-099, 150-199, 277-299
	Y	A001	9J	W0176	19H	24		73-21-18	275-276
	Y	A001	BJ	W0176	63L	24		73-21-18	ALL
	Y	A001	BJ	W0176	63N	24		73-21-18	ALL
	Y	A002	BJ	W0176	46F	22		36-11-61	ALL
	Y	A002	BJ	W0176	55F	22		36-11-61	ALL
	Y	A002	BJ	W0176	72E	22		36-11-61	050-099, 150-156, 162-166, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 23

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0220		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
	Y	A002	BJ	W0176	805	22		36-11-61	050-099, 150-155, 157, 167-199, 275-299
	X	A003	BJ	W0176	246B	24		28-41-11	ALL
	X	A003	BJ	W0184	206B	24		28-41-11	ALL
	X	A006	BJ	W0180	108	24		21-58-12	ALL
	X	A006	BJ	W0184	76A	24		21-58-12	ALL
	X	A007	BJ	W0176	890	24		21-58-16	ALL
	X	A007	BJ	W0184	831	24		21-58-16	ALL
	X	A009	BJ	W0180	001	24		21-53-12	ALL
	X	A009	BJ	W0182	012	24		21-53-12	ALL
	X	A010	BJ	W0180	005	24		21-53-12	ALL
	X	A010	BJ	W0182	030	24		21-53-12	ALL
	Y	A012	BJ	W0176	01C	24		21-25-11	ALL
	Y	A012	BJ	W0176	522	24		21-25-11	ALL
	Y	A012	BJ	W0176	524	24		21-25-11	ALL
	Y	A012	BJ	W0176	529	24		21-25-11	ALL
	X	A014	BJ	W0180	012	24		21-58-16	ALL
	X	A014	BJ	W0184	583	24		21-58-16	ALL
	X	A016	BJ	W0176	684	22		73-21-19	275-299
	X	A016	BJ	W0184	08A	22		73-21-19	275-299
	Y	A019	BJ	W0176	02R	24		78-36-11	ALL
	Y	A019	BJ	W0176	03T	20		78-34-11	ALL
	Y	A019	BJ	W0176	22W	20		78-34-11	ALL
	Y	A02	BJ	W0176	805	22		36-11-61	156, 162-166
	Y	A020	BJ	W0176	172	24		24-22-11	ALL
	Y	A020	BJ	W0176	666	24		24-22-11	ALL
	Y	A020	BJ	W0180	002	24		24-22-22	ALL
	X	B003	BJ	W0176	246R	24		28-41-11	ALL
	X	B003	BJ	W0184	206R	24		28-41-11	ALL
	X	B004	BJ	W0056	006	20		25-42-11	ALL
	X	B004	BJ	W0182	70A	20		25-42-11	ALL
	X	B005	BJ	W0176	752	22		27-09-12	ALL
	X	B005	BJ	W0180	017	22		27-09-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 24

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0220		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
	X	B006	BJ	W0180	109	24		21-58-12	ALL
	X	B006	BJ	W0184	76B	24		21-58-12	ALL
	X	B007	BJ	W0176	891	24		21-58-16	ALL
	X	B007	BJ	W0184	832	24		21-58-16	ALL
	X	B009	BJ	W0180	007	24		21-53-12	ALL
	X	B009	BJ	W0182	024	24		21-53-12	ALL
	X	B010	BJ	W0180	006	24		21-53-12	ALL
	X	B010	BJ	W0182	020	24		21-53-12	ALL
	X	B014	BJ	W0180	013	24		21-58-16	ALL
	X	B014	BJ	W0184	584	24		21-58-16	ALL
	X	B015	BJ	W0176	851	24		21-53-12	ALL
	X	B015	BJ	W0180	084	24		21-53-12	ALL
	X	B016	BJ	W0176	064	22		52-11-12	050-099, 150-199
	X	B016	BJ	W0176	064	20		52-11-12	275-299
	X	B016	BJ	W0180	038	22		52-11-12	050-099, 150-199
	X	B016	BJ	W0180	038	20		52-11-12	275-299
	Y	C002	BJ	W0176	02X	24		78-36-11	ALL
	Y	C002	BJ	W0176	811	24		78-34-11	ALL
	Y	C002	BJ	W0176	84B	22		78-34-11	ALL
	X	C004	BJ	W0176	661	24		32-31-11	ALL
	X	C004	BJ	W0180	035	24		32-31-11	ALL
	X	C005	BJ	W0180	027	24		36-23-21	ALL
	X	C005	BJ	W0184	011	24		36-23-21	ALL
	X	C007	BJ	W0176	892	24		21-58-16	ALL
	X	C007	BJ	W0184	833	24		21-58-16	ALL
	X	C009	BJ	W0180	003	24		21-53-12	ALL
	X	C009	BJ	W0182	016	24		21-53-12	ALL
	X	C010	BJ	W0176	058	24		21-58-14	ALL
	X	C010	BJ	W0184	058	24		21-58-14	ALL
	Y	C011	BJ	W0180	016	24		21-58-16	ALL
	Y	C011	BJ	W0184	065	24		21-58-16	ALL
	Y	C011	BJ	W0184	579	24		21-58-16	ALL
	X	C014	BJ	W0180	061	24		21-44-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 25

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0220		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0220	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
	X	C014	BJ	W0182	107	24		21-44-21	ALL
	X	C016	BJ	W0176	074	24		33-16-14	ALL
	X	C016	BJ	W0184	195	24		33-16-14	ALL
	F	C018	2	W0176	759	18		28-41-12	ALL
	F	C018	2	W0184	837	18		28-41-12	ALL
	Y	C019	BJ	W0176	01A	24		21-25-11	ALL
	Y	C019	BJ	W0176	01B	24		21-25-11	ALL
	Y	C019	BJ	W0176	523	22		21-25-11	ALL
	Y	C020	BJ	W0176	061	22		52-11-12	050-099, 150-199
	Y	C020	BJ	W0176	061	20		52-11-12	275-299
	Y	C020	BJ	W0176	065	22		52-11-12	ALL
	Y	C020	BJ	W0180	037	22		52-11-12	050-099, 150-199
	Y	C020	BJ	W0180	037	20		52-11-12	275-299
	X	D007	BJ	W0176	563	22		29-11-12	ALL
	X	D007	BJ	W0180	154	22		29-11-12	ALL
	X	D009	BJ	W0180	004	24		21-53-12	ALL
	X	D009	BJ	W0182	027	24		21-53-12	ALL
	X	D016	BJ	W0176	075	24		33-16-14	ALL
	X	D016	BJ	W0180	075	24		33-16-14	ALL
	X	DED		W0176	058Z			21-58-14	ALL
	X	DED		W0176	563Z			29-11-12	ALL
	X	DED		W0176	752Z			27-09-12	ALL
	F	DED		W0176	759Z			28-41-12	ALL
	X	DED		W0180	017Z			27-09-12	ALL
	X	DED		W0180	154Z			29-11-12	ALL
	X	DED		W0184	058Z			21-58-14	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 26

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0222		BACT44B0910U					P036-00/ /		ALL
TB0222	F	BACM15C1A					P036-00/ /		150-199, 275-299
TB0222	G	BACM15C1B					P036-00/ /		ALL
TB0222	H	BACM15C2A					P036-00/ /		ALL
TB0222	X	BACM15C3A					P036-00/ /		ALL
TB0222	Y	BACM15C3B					P036-00/ /		ALL
TB0222	Z	BACM15C3C					P036-00/ /		ALL
	H	11	2	W0182	118	18		38-32-11	050-099, 150-155, 162-165
	H	11	2	W0182	119	22		38-32-11	050-099, 275-299
	H	11	2	W0182	119	20		38-32-11	150-199
	H	11	2	W0182	124	22		38-32-11	050-099, 155, 165, 275-276
	H	11	2	W0182	124	20		38-32-11	150-154, 156-164, 166-199
	H	11	2	W0182	124	18		38-32-11	277-299
	H	11	2	W0182	125	18		38-32-12	050, 150-155, 162-165, 275-276
	H	11	2	W0182	125	18		38-32-11	051-099, 156-157, 166-199, 277-299
	H	11	2	W0182	126	18		38-32-12	050-099, 150-155, 162-165, 275-276
	H	11	2	W0182	155	20		38-32-14	275-276
	H	11	2	W0182	171	18		38-32-11	275-276
	Z	15	BJ	W0176	80L	22		30-21-11	050-099, 150-199
	Z	15	BJ	W0176	80M	22		30-21-11	050-099, 150-199
	Z	15	BJ	W0176	81E	22		30-21-11	050-099, 150-199
	Z	15	BJ	W0176	81F	22		30-21-11	050-099, 150-199
	Z	15	BJ	W0176	839	22		30-21-11	050-099, 150-199
	Z	15	BJ	W0176	881	22		30-21-11	050-099, 150-199
	Z	16	BJ	W0176	272	22		30-21-11	050-099, 150-199
	Z	16	BJ	W0176	80N	22		30-21-11	050-099, 150-199
	Z	16	BJ	W0176	80R	22		30-21-11	050-099, 150-199
	Z	16	BJ	W0176	80T	22		30-21-11	050-099, 150-199
	Z	16	BJ	W0176	823	24		30-21-11	050-099, 150-199
	Z	3	BJ	W0180	029	24		21-53-12	ALL
	Z	3	BJ	W0182	011	24		21-53-12	ALL
	Z	3	BJ	W0182	015	24		21-53-12	ALL
	Z	3	BJ	W0182	019	24		21-53-12	ALL
	Z	3	BJ	W0182	023	24		21-53-12	ALL
	Z	3	BJ	W0182	026	24		21-53-12	ALL
	Z	3	BJ	W0182	029	24		21-53-12	ALL
	Z	4	BJ	W0180	031	24		21-53-12	ALL
	Z	4	BJ	W0182	010	24		21-53-12	ALL
	Z	4	BJ	W0182	014	24		21-53-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 27

Feb 06/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0222		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0222	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	4	BJ	W0182	018	24		21-53-12	ALL
	Z	4	BJ	W0182	022	24		21-53-12	ALL
	Z	4	BJ	W0182	025	24		21-53-12	ALL
	Z	4	BJ	W0182	028	24		21-53-12	ALL
	G	5	2	W0056	032	18		28-26-11	ALL
	G	5	2	W0184	537	18		28-26-11	ALL
	G	5	2	W0184	538	20		28-26-11	ALL
	G	6	2	W0056	044	16		38-13-11	ALL
	G	6	2	W0182	002	16		38-13-11	ALL
	X	A001	BJ	W0056	009	20		21-45-11	ALL
	X	A001	BJ	W0176	801	20		21-45-11	ALL
	X	A007	BJ	W0056	003	22		23-34-11	ALL
	X	A007	BJ	W0176	576	22		23-34-11	ALL
	X	A010	BJ	W0056	049	20		30-41-11	ALL
	X	A010	BJ	W0182	112	20		30-41-11	ALL
	X	A013	BJ	W0176	01S	24		21-58-11	ALL
	X	A013	BJ	W0184	773	24		21-58-11	ALL
	Y	A015	BJ	W0176	20RB	24		34-45-14	275-299
	Y	A016	BJ	W0176	909	22		34-53-11	275-299
	Y	A016	BJ	W0176	911B	24		34-53-11	275-299
	X	A017	BJ	W0176	017	24		21-44-21	275-276
	X	A017	BJ	W0182	034	24		21-44-21	275-276
	X	A018	BJ	W0056	075	20		21-66-31	050-099, 150, 152-199
	X	A018	BJ	W0176	31E	20		21-66-31	050-099, 150, 152-199
	Y	A019	BJ	W0176	152	24		21-51-11	150-199, 275-299
	Y	A019	BJ	W0176	158	24		21-51-11	150-199, 275-299
	Y	A019	BJ	W0176	557	24		21-51-11	150-199, 275-299
	Y	A020	BJ	W0176	20RB	24		34-45-14	050-099, 150-199
	Y	A020	BJ	W0176	220B	24		27-32-11	ALL
	Y	A020	BJ	W0176	221B	24		32-42-11	ALL
	Y	A020	BJ	W0176	226B	24		32-42-11	ALL
	Y	A020	BJ	W0176	909	22		34-53-11	275-299
	X	B002	BJ	W0176	05A	22		74-31-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 28

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0222		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0222	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	X	B002	BJ	W0184	720	22		74-31-11	ALL
	X	B007	BJ	W0176	875	22		74-31-11	ALL
	X	B007	BJ	W0184	721	22		74-31-11	ALL
	X	B008	BJ	W0056	035	20		28-26-11	ALL
	X	B008	BJ	W0184	570	20		28-26-11	ALL
	X	B009	BJ	W0056	028	24		21-44-11	ALL
	X	B009	BJ	W0182	046	24		21-44-11	ALL
	X	B010	BJ	W0056	046	24		21-43-11	ALL
	X	B010	BJ	W0182	043	24		21-43-11	ALL
	X	B017	BJ	W0176	018	24		21-44-21	275-276
	X	B017	BJ	W0182	035	24		21-44-21	275-276
	X	B018	BJ	W0056	082	20		21-66-31	050-099, 150, 152-199
	X	B018	BJ	W0176	41E	20		21-66-31	050-099, 150, 152-199
	X	C001	BJ	W0056	047	24		21-44-21	ALL
	X	C001	BJ	W0182	105	24		21-44-21	ALL
	X	C002	BJ	W0176	719	22		74-31-11	ALL
	X	C002	BJ	W0184	722	22		74-31-11	ALL
	X	C007	BJ	W0176	173	22		74-31-11	ALL
	X	C007	BJ	W0184	723	22		74-31-11	ALL
	X	C009	BJ	W0056	045	24		36-23-11	ALL
	X	C009	BJ	W0176	772	24		36-23-11	ALL
	X	C010	BJ	W0176	70J	20		38-32-11	050-099, 155-199, 277-299
	X	C010	BJ	W0176	70J	20		SPARE	276
	X	C010	BJ	W0182	156	20		38-32-11	050-099, 155-199, 277-299
	X	C010	BJ	W0182	156	20		SPARE	276
	X	C013	BJ	W0176	089	24		21-58-16	ALL
	X	C013	BJ	W0184	074	24		21-58-16	ALL
	Y	C015	BJ	W0176	20RZ			34-45-14	275-299
	Y	C015	BJ	W0176	910	22		34-53-11	275-299
	Y	C015	BJ	W0176	911Z			34-53-11	275-299
	Y	C016	BJ	W0176	20RR	24		34-45-14	275-299
	Y	C016	BJ	W0176	908	22		34-53-11	275-299
	Y	C016	BJ	W0176	911R	24		34-53-11	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 29

Feb 06/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0222		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>150-199, 275-299</b>
TB0222	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0222	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	X	C017	BJ	W0056	077	20		21-66-31	050-099, 150, 152-199
	X	C017	BJ	W0176	33E	20		21-66-31	050-099, 150, 152-199
	X	C018	BJ	W0056	081	20		21-66-31	050-099, 150, 152-199
	X	C018	BJ	W0176	47E	20		21-66-31	050-099, 150, 152-199
	Y	C019	BJ	W0176	20RZ			34-45-14	050-099, 150-199
	Y	C019	BJ	W0176	220Z			27-32-11	ALL
	Y	C019	BJ	W0176	221Z			32-42-11	ALL
	Y	C019	BJ	W0176	226Z			32-42-11	ALL
	Y	C019	BJ	W0176	910	22		34-53-11	275-299
	Y	C020	BJ	W0176	20RR	24		34-45-14	050-099, 150-199
	Y	C020	BJ	W0176	220R	24		27-32-11	ALL
	Y	C020	BJ	W0176	221R	24		32-42-11	ALL
	Y	C020	BJ	W0176	226R	24		32-42-11	ALL
	Y	C020	BJ	W0176	908	22		34-53-11	275-299
	X	CAP	Y	W0176	017	24		SPARE	051-099, 150-154
	X	CAP	Y	W0176	018	24		SPARE	051-099, 150-154
	X	CAP	Y	W0182	034	24		SPARE	051-099, 150-154
	X	CAP	Y	W0182	035	24		SPARE	051-099, 150-154
	X	D002	BJ	W0056	010	20		21-45-11	ALL
	X	D002	BJ	W0176	670	20		21-45-11	ALL
	X	D007	BJ	W0056	036	20		28-26-11	ALL
	X	D007	BJ	W0184	552	20		28-26-11	ALL
	X	D009	BJ	W0056	048	20		30-41-11	ALL
	X	D009	BJ	W0182	111	20		30-41-11	ALL
	X	D010	BJ	W0056	007	22		23-31-12	ALL
	X	D010	BJ	W0176	125	22		23-31-12	ALL
	X	D013	BJ	W0056	074	22		21-66-31	050-099, 150, 152-199
	X	D013	BJ	W0176	29E	22		21-66-31	050-099, 150, 152-199
	X	D017	BJ	W0056	076	20		21-66-31	050-099, 150, 152-199
	X	D017	BJ	W0176	32E	20		21-66-31	050-099, 150, 152-199
	X	D018	BJ	W0056	080	20		21-66-31	050-099, 150, 152-199
	X	D018	BJ	W0176	46E	20		21-66-31	050-099, 150, 152-199
	X	DED		W0176	05AZ			74-31-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 30

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0222		BACT44B0910U (continued)					P036-00/ /		ALL
TB0222	F	BACM15C1A (continued)					P036-00/ /		150-199, 275-299
TB0222	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0222	H	BACM15C2A (continued)					P036-00/ /		ALL
TB0222	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0222	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0222	Z	BACM15C3C (continued)					P036-00/ /		ALL
	X	DED		W0176	719Z			74-31-11	ALL
	X	DED		W0184	720Z			74-31-11	ALL
	X	DED		W0184	722Z			74-31-11	ALL
TB0237	R	RESISTORBLOCK-REF284T1067-					SHELF/E08/00		ALL
TB0237	X	BACM15C3A					SHELF/E08/00		ALL
TB0237	Y	BACM15C3B					SHELF/E08/00		ALL
TB0237	Z	BACM15C3C					SHELF/E08/00		ALL
	X			W2004	201Z			31-41-31	050-099, 150-199
	Z			W2004	201Z			31-41-31	275-299
	X			W2004	205Z			31-41-32	050-099, 150-199
	Z			W2004	205Z			31-41-32	275-299
	X			W2006	201Z			31-41-33	050-099, 150-199
	Z			W2006	201Z			31-41-33	275-299
	X			W2006	205Z			31-41-34	050-099, 150-199
	Z			W2006	205Z			31-41-34	275-299
	Z	10	BJ	W2000	BK16	24		21-64-11	ALL
	Z	10	BJ	W2000	BM18	24		21-64-11	ALL
	Z	10	BJ	W2000	DN18	24		21-64-11	ALL
	Z	10	BJ	W2000	FN10	24		21-64-11	ALL
	Z	10	BJ	W2000	PM02	24		21-52-21	ALL
	Z	10	BJ	W2004	026	22		31-41-32	ALL
	Z	10	BJ	W2006	025	22		31-41-32	ALL
	Z	17	BJ	W2000	DL11	24		21-52-11	ALL
	Z	17	BJ	W2000	FK05	24		21-52-11	ALL
	Z	17	BJ	W2004	029	22		31-41-34	ALL
	Z	17	BJ	W2006	030	22		31-41-34	ALL
	Z	18	BJ	W2000	NN12	24		79-31-11	ALL
	Z	18	BJ	W2000	PM05	24		21-52-21	ALL
	Z	18	BJ	W2000	PN11	24		21-52-21	ALL
	Z	18	BJ	W2000	RM11	24		24-11-21	ALL
	Z	18	BJ	W2002	PL19	24		49-94-14	ALL
	Z	18	BJ	W2006	029	22		31-41-34	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 31

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity	
TB0237	R	<b>RESISTORBLOCK-REF284T1067- (continued)</b>						<b>SHELF/E08/00</b>		<b>ALL</b>
TB0237	X	<b>BACM15C3A (continued)</b>						<b>SHELF/E08/00</b>		<b>ALL</b>
TB0237	Y	<b>BACM15C3B (continued)</b>						<b>SHELF/E08/00</b>		<b>ALL</b>
TB0237	Z	<b>BACM15C3C (continued)</b>						<b>SHELF/E08/00</b>		<b>ALL</b>
	Z	18	BJ	W2006	030	22		31-41-34	ALL	
	Z	3	BJ	W2004	201R	24		31-41-31	275-299	
	Z	3	BJ	W2004	205R	24		31-41-32	275-299	
	Z	4	BJ	W2004	201B	24		31-41-31	275-299	
	Z	4	BJ	W2004	205B	24		31-41-32	275-299	
	Z	5	BJ	W2006	201R	24		31-41-33	275-299	
	Z	5	BJ	W2006	205R	24		31-41-34	275-299	
	Z	6	BJ	W2006	201B	24		31-41-33	275-299	
	Z	6	BJ	W2006	205B	24		31-41-34	275-299	
	Z	9	BJ	W2000	FK02	24		21-52-11	ALL	
	Z	9	BJ	W2000	FL04	24		21-64-11	ALL	
	Z	9	BJ	W2000	FL07	24		21-64-11	ALL	
	Z	9	BJ	W2000	GL12	24		79-31-11	ALL	
	Z	9	BJ	W2000	HK11	24		24-11-11	ALL	
	Z	9	BJ	W2002	EK14	24		21-64-11	ALL	
	Z	9	BJ	W2004	025	22		31-41-32	ALL	
	Z	9	BJ	W2004	026	22		31-41-32	ALL	
	Y	A001	BJ	W2004	008	24		24-25-13	ALL	
	Y	A001	BJ	W2004	018	24		24-25-13	ALL	
	Y	A001	BJ	W2004	038	24		24-25-13	ALL	
	X	A003	BJ	W2004	201R	24		31-41-31	050-099, 150-199	
	X	A003	BJ	W2004	205R	24		31-41-32	050-099, 150-199	
	X	A007	BJ	W2000	TK12	24		27-09-14	ALL	
	X	A007	BJ	W2002	RM04	24		27-09-14	ALL	
	X	A008	BJ	W2000	TK13	24		27-09-14	ALL	
	X	A008	BJ	W2002	RM05	24		27-09-14	ALL	
	X	A013	BJ	W2004	207R	24		31-41-32	ALL	
	X	A013	BJ	W2006	209R	24		31-41-32	ALL	
	X	A014	BJ	W2004	207Z			31-41-32	ALL	
	X	A014	BJ	W2006	209Z			31-41-32	ALL	
	X	A015	BJ	W2000	AK10	24		79-32-11	ALL	
	X	A015	BJ	W2000	AM07	24		79-32-11	ALL	
	R	A019	2	W2006	032	20		49-71-11	ALL	
	R	A020	2	W2006	034	20		49-73-11	ALL	
	X	B003	BJ	W2004	201B	24		31-41-31	050-099, 150-199	
	X	B003	BJ	W2004	205B	24		31-41-32	050-099, 150-199	
	X	B007	BJ	W1037	228R	24		31-31-13	ALL	

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 32

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity	
TB0237	R	<b>RESISTORBLOCK-REF284T1067- (continued)</b>						<b>SHELF/E08/00</b>		<b>ALL</b>
TB0237	X	<b>BACM15C3A (continued)</b>						<b>SHELF/E08/00</b>		<b>ALL</b>
TB0237	Y	<b>BACM15C3B (continued)</b>						<b>SHELF/E08/00</b>		<b>ALL</b>
TB0237	Z	<b>BACM15C3C (continued)</b>						<b>SHELF/E08/00</b>		<b>ALL</b>
	X	B007	BJ	W2002	CL02	24		31-31-13	ALL	
	X	B008	BJ	W1035	067	24		31-31-13	ALL	
	X	B008	BJ	W2002	CL05	24		31-31-13	ALL	
	X	B013	BJ	W2004	207B	24		31-41-32	ALL	
	X	B013	BJ	W2006	209B	24		31-41-32	ALL	
	X	B015	BJ	W2000	MK10	24		79-32-11	ALL	
	X	B015	BJ	W2000	MM07	24		79-32-11	ALL	
	Y	C001	BJ	W2004	009	24		24-25-13	ALL	
	Y	C001	BJ	W2004	019	24		24-25-13	ALL	
	Y	C001	BJ	W2004	039	24		24-25-13	ALL	
	X	C003	BJ	W2006	201R	24		31-41-33	050-099, 150-199	
	X	C003	BJ	W2006	205R	24		31-41-34	050-099, 150-199	
	X	C007	BJ	W1037	228B	24		31-31-13	ALL	
	X	C007	BJ	W2002	CL03	24		31-31-13	ALL	
	X	C008	BJ	W2000	TK11	24		27-09-14	ALL	
	X	C008	BJ	W2002	RM13	24		27-09-14	ALL	
	X	C013	BJ	W2004	209R	24		31-41-34	ALL	
	X	C013	BJ	W2006	207R	24		31-41-34	ALL	
	X	C014	BJ	W2000	FL03	24		21-64-11	ALL	
	X	C014	BJ	W2002	EM13	24		21-64-11	ALL	
	R	C019	2	W2002	HM05	24		49-71-11	ALL	
	R	C019	2	W2006	031	22		49-71-11	ALL	
	R	C020	2	W2002	HM07	24		49-73-11	ALL	
	R	C020	2	W2006	033	22		49-73-11	ALL	
	Z	CAP	Y	W2002	CL17	24		SPARE	ALL	
	Z	CAP	Y	W2002	CL18	24		SPARE	ALL	
	Z	CAP	Y	W2002	CN17	24		SPARE	ALL	
	Z	CAP	Y	W2002	CN18	24		SPARE	ALL	
	X	D003	BJ	W2006	201B	24		31-41-33	050-099, 150-199	
	X	D003	BJ	W2006	205B	24		31-41-34	050-099, 150-199	
	X	D007	BJ	W1037	228Z			31-31-13	ALL	
	X	D007	BJ	W2002	CL04	24		31-31-13	ALL	
	X	D008	BJ	W2000	TL07	24		27-09-14	ALL	
	X	D008	BJ	W2002	RM16	24		27-09-14	ALL	
	X	D013	BJ	W2004	209B	24		31-41-34	ALL	
	X	D013	BJ	W2006	207B	24		31-41-34	ALL	
	X	D014	BJ	W2004	209Z			31-41-34	ALL	

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 33

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity	
TB0237	R	RESISTORBLOCK-REF284T1067- (continued)						SHELF/E08/00		ALL
TB0237	X	BACM15C3A (continued)						SHELF/E08/00		ALL
TB0237	Y	BACM15C3B (continued)						SHELF/E08/00		ALL
TB0237	Z	BACM15C3C (continued)						SHELF/E08/00		ALL
	X	D014	BJ	W2006	207Z			31-41-34	ALL	
TB0239		BACM15C3B						SHELF/E08/00		ALL
TB0239	X	BACM15C3A						SHELF/E08/00		ALL
TB0239	Y	BACM15C3B						SHELF/E08/00		ALL
TB0239	Z	BACM15C3C						SHELF/E08/00		ALL
	Z		%	W1035	106	24		SPARE	150-199	
	Z		%	W1037	085	24		SPARE	150-199	
	Z	10	BJ	W1035	051	22		31-41-15	ALL	
	Z	10	BJ	W1035	053	22		31-41-15	151, 166	
	Z	10	%	W1035	053	22		31-41-15	165, 167-199	
	Z	10	BJ	W1035	054	22		31-41-15	ALL	
	Z	10	BJ	W1035	055	22		31-41-15	151, 166	
	Z	10	%	W1035	055	22		31-41-15	165, 167-199	
	Z	10	BJ	W1035	087	22		31-41-15	ALL	
	Z	10	BJ	W1035	088	22		31-41-15	ALL	
	Z	10	BJ	W1035	095	22		31-41-15	ALL	
	Z	31	BJ	W1037	046	22		31-41-15	ALL	
	Z	31	BJ	W1037	066	22		31-41-15	ALL	
	Z	32	BJ	W1037	042	22		31-41-15	ALL	
	Z	32	BJ	W1037	044	22		31-41-15	151, 166	
	Z	32	%	W1037	044	22		31-41-15	165, 167-199	
	Z	32	BJ	W1037	045	22		31-41-15	151, 166	
	Z	32	%	W1037	045	22		31-41-15	165, 167-199	
	Z	32	BJ	W1037	074	22		31-41-15	ALL	
	Z	32	BJ	W1037	075	22		31-41-15	ALL	
	Z	32	BJ	W1037	099	22		31-41-15	ALL	
	Z	33	BJ	W1037	090	22		31-41-15	ALL	
	Z	34	BJ	W1035	060	24		31-41-17	ALL	
	Z	34	BJ	W1037	051	24		31-41-17	ALL	
	Z	34	BJ	W2006	007	22		31-41-17	ALL	
	Z	35	BJ	W1035	061	24		31-41-17	ALL	
	Z	35	BJ	W1035	062	22		31-41-17	ALL	
	Z	35	BJ	W1035	067	24		31-31-13	ALL	
	Z	35	BJ	W1037	052	24		31-41-17	ALL	
	Z	36	BJ	W1035	063	22		31-41-17	ALL	
	Z	36	BJ	W1035	064	24		31-41-17	ALL	

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 34

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0239		<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Z	<b>BACM15C3C (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
	Z	36	BJ	W1035	065	24		31-41-17	ALL
	Z	37	BJ	W1037	050	22		31-41-15	ALL
	Z	37	BJ	W1037	091	22		31-41-15	ALL
	Z	38	BJ	W1035	051	22		31-41-15	ALL
	Z	38	BJ	W1035	052	20		31-41-15	ALL
	Z	38	BJ	W1035	080	22		31-41-15	ALL
	Z	38	BJ	W1035	090	22		31-41-15	ALL
	Z	38	BJ	W1035	091	22		31-41-15	ALL
	Z	39	BJ	W1037	042	22		31-41-15	ALL
	Z	39	BJ	W1037	043	20		31-41-15	ALL
	Z	39	BJ	W1037	066	22		31-41-15	ALL
	Z	39	BJ	W1037	090	22		31-41-15	ALL
	Z	39	BJ	W1037	091	22		31-41-15	ALL
	Z	7	BJ	W1035	091	22		31-41-15	ALL
	Z	8	BJ	W1035	090	22		31-41-15	ALL
	Z	9	BJ	W1035	056	22		31-41-15	ALL
	Z	9	BJ	W1035	080	22		31-41-15	ALL
	Y	A001	BJ	W1037	001	24		31-41-12	ALL
	Y	A001	BJ	W1037	004	24		31-41-12	ALL
	Y	A001	BJ	W1037	007	24		31-41-12	ALL
	Y	A002	BJ	W1037	002	24		31-41-12	ALL
	Y	A002	BJ	W1037	005	24		31-41-12	ALL
	Y	A002	BJ	W1037	008	24		31-41-12	ALL
	X	A011	BJ	W1035	019	24		31-41-15	ALL
	X	A011	BJ	W1035	053	22		31-41-15	165-199
	X	A012	BJ	W1035	020	24		31-41-15	ALL
	X	A012	BJ	W1035	087	22		31-41-15	ALL
	X	A013	BJ	W1035	021	24		31-41-15	ALL
	X	A014	BJ	W1035	022	24		31-41-15	ALL
	X	A014	BJ	W1035	095	22		31-41-15	ALL
	X	A015	BJ	W1035	023	24		31-41-15	ALL
	X	A015	BJ	W1035	054	22		31-41-15	ALL
	X	A016	BJ	W1035	024	24		31-41-15	ALL
	X	A016	BJ	W1035	055	22		31-41-15	151, 165-199
	X	A017	BJ	W1035	025	24		31-41-15	ALL
	X	A017	BJ	W1035	088	22		31-41-15	ALL
	X	A018	BJ	W1035	026	24		31-41-15	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 35

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0239		<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Z	<b>BACM15C3C (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
	X	A019	BJ	W1035	027	24		31-41-15	ALL
	X	A020	BJ	W1035	028	24		31-41-15	ALL
	X	A021	BJ	W1037	010	24		31-41-15	ALL
	X	A021	BJ	W1037	044	22		31-41-15	151, 165-199
	X	A022	BJ	W1037	011	24		31-41-15	ALL
	X	A022	BJ	W1037	074	22		31-41-15	ALL
	X	A023	BJ	W1037	012	24		31-41-15	ALL
	X	A024	BJ	W1037	013	24		31-41-15	ALL
	X	A024	BJ	W1037	099	22		31-41-15	ALL
	X	A025	BJ	W1037	014	24		31-41-15	ALL
	X	A026	BJ	W1037	015	24		31-41-15	ALL
	X	A026	BJ	W1037	045	22		31-41-15	151, 165-199
	X	A027	BJ	W1037	016	24		31-41-15	ALL
	X	A027	BJ	W1037	075	22		31-41-15	ALL
	X	A028	BJ	W1037	017	24		31-41-15	ALL
	X	A029	BJ	W1037	018	24		31-41-15	ALL
	X	A030	BJ	W1037	019	24		31-41-15	ALL
	Y	A041	BJ	W1039	013	24		27-18-11	155-157, 166-199, 277-299
	Y	A041	BJ	W1039	019	24		27-18-11	155-157, 166-199, 277-299
	Y	A041	BJ	W2006	035	24		27-18-11	155-157, 166-199, 277-299
	Y	A042	BJ	W1039	017	24		27-18-11	155-157, 166-199, 277-299
	Y	A042	BJ	W1039	021	24		27-18-11	155-157, 166-199, 277-299
	Y	A042	BJ	W2006	037	24		27-18-11	155-157, 166-199, 277-299
	Y	A043	BJ	W1039	023	24		27-18-11	155-157, 166-199, 277-299
	Y	A043	BJ	W1039	027	24		27-18-11	155-157, 166-199, 277-299
	Y	A043	BJ	W2006	039	24		27-18-11	155-157, 166-199, 277-299
	Y	A043	BJ	W2006	043	24		27-18-11	155-157, 166-199, 277-299
	Y	A044	BJ	W1039	025	24		27-18-11	155-157, 166-199, 277-299
	Y	A044	BJ	W1039	030	24		27-18-11	155-157, 166-199, 277-299
	Y	A044	BJ	W2006	040	24		27-18-11	155-157, 166-199, 277-299
	Y	A044	BJ	W2006	045	24		27-18-11	155-157, 166-199, 277-299
	X	AO11	BJ	W1035	053	22		31-41-15	151
	X	B011	BJ	W1035	029	24		31-41-15	ALL
	X	B011	BJ	W1035	056	22		31-41-15	ALL
	X	B012	BJ	W1035	030	24		31-41-15	ALL
	X	B013	BJ	W1035	031	24		31-41-15	ALL
	X	B014	BJ	W1035	032	24		SPARE	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 36

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0239		<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Z	<b>BACM15C3C (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
	X	B015	BJ	W1035	033	24		SPARE	ALL
	X	B016	BJ	W1035	034	24		SPARE	ALL
	X	B017	BJ	W1035	035	24		SPARE	ALL
	X	B018	BJ	W1035	036	24		SPARE	ALL
	X	B019	BJ	W1035	037	24		SPARE	ALL
	X	B020	BJ	W1035	038	24		SPARE	ALL
	X	B021	BJ	W1037	020	24		31-41-15	ALL
	X	B021	BJ	W1037	046	22		31-41-15	ALL
	X	B022	BJ	W1037	021	24		31-41-15	ALL
	X	B023	BJ	W1037	022	24		31-41-15	ALL
	X	B024	BJ	W1037	023	24		SPARE	ALL
	X	B025	BJ	W1037	024	24		SPARE	ALL
	X	B026	BJ	W1037	025	24		SPARE	ALL
	X	B027	BJ	W1037	026	24		SPARE	ALL
	X	B028	BJ	W1037	027	24		SPARE	ALL
	X	B029	BJ	W1037	028	24		SPARE	ALL
	X	B030	BJ	W1037	029	24		SPARE	ALL
	Y	C001	BJ	W1035	001	24		31-41-12	ALL
	Y	C001	BJ	W1035	004	24		31-41-12	ALL
	Y	C001	BJ	W1035	007	24		31-41-12	ALL
	Y	C002	BJ	W1035	002	24		31-41-12	ALL
	Y	C002	BJ	W1035	005	24		31-41-12	ALL
	Y	C002	BJ	W1035	008	24		31-41-12	ALL
	Y	C004	BJ	W1035	012	24		31-41-16	ALL
	Y	C004	BJ	W1035	013	24		31-41-16	ALL
	Y	C004	BJ	W1035	016	24		31-41-16	ALL
	Y	C005	BJ	W1035	010	24		31-41-16	ALL
	Y	C005	BJ	W1035	014	24		31-41-16	ALL
	Y	C005	BJ	W1035	017	24		31-41-16	ALL
	X	C011	BJ	W1035	039	24		SPARE	ALL
	X	C012	BJ	W1035	040	24		SPARE	ALL
	X	C013	BJ	W1035	041	24		SPARE	ALL
	X	C014	BJ	W1035	042	24		SPARE	ALL
	X	C015	BJ	W1035	043	24		SPARE	ALL
	X	C016	BJ	W1035	044	24		SPARE	ALL
	X	C017	BJ	W1035	045	24		SPARE	ALL
	X	C018	BJ	W1035	046	24		SPARE	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 37

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0239		<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Z	<b>BACM15C3C (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
	X	C019	BJ	W1035	047	24		SPARE	ALL
	X	C020	BJ	W1035	048	24		31-41-15	ALL
	X	C021	BJ	W1037	030	24		SPARE	ALL
	X	C022	BJ	W1037	031	24		SPARE	ALL
	X	C023	BJ	W1037	032	24		SPARE	ALL
	X	C024	BJ	W1037	033	24		SPARE	ALL
	X	C025	BJ	W1037	034	24		SPARE	ALL
	X	C026	BJ	W1037	035	24		SPARE	ALL
	X	C027	BJ	W1037	036	24		SPARE	ALL
	X	C028	BJ	W1037	037	24		SPARE	ALL
	X	C029	BJ	W1037	038	24		SPARE	ALL
	X	C030	BJ	W1037	039	24		31-41-15	ALL
	Y	C041	BJ	W1039	014	24		27-18-11	155-157, 166-199, 277-299
	Y	C041	BJ	W1039	020	24		27-18-11	155-157, 166-199, 277-299
	Y	C041	BJ	W2006	036	24		27-18-11	155-157, 166-199, 277-299
	Y	C041	BJ	W2006	041	24		27-18-11	155-157, 166-199, 277-299
	Y	C042	BJ	W1039	018	24		27-18-11	155-157, 166-199, 277-299
	Y	C042	BJ	W1039	022	24		27-18-11	155-157, 166-199, 277-299
	Y	C042	BJ	W2006	038	24		27-18-11	155-157, 166-199, 277-299
	Y	C042	BJ	W2006	042	24		27-18-11	155-157, 166-199, 277-299
	Y	C043	BJ	W1039	024	24		27-18-11	155-157, 166-199, 277-299
	Y	C043	BJ	W1039	028	24		27-18-11	155-157, 166-199, 277-299
	Y	C043	BJ	W2006	044	24		27-18-11	155-157, 166-199, 277-299
	Y	C044	BJ	W1039	026	24		27-18-11	155-157, 166-199, 277-299
	Y	C044	BJ	W1039	032	24		27-18-11	155-157, 166-199, 277-299
	Y	C044	BJ	W2006	046	24		27-18-11	155-157, 166-199, 277-299
	X	D011	BJ	W1035	049	24		31-41-15	ALL
	X	D012	BJ	W1035	050	24		31-41-15	ALL
	X	D021	BJ	W1037	040	24		31-41-15	ALL
	X	D022	BJ	W1037	041	24		31-41-15	ALL
	X	D022	BJ	W1037	050	22		31-41-15	ALL
	Z	DED		W1035	060Z			31-41-17	ALL
	Z	REF	%	W1035	104	24		SPARE	ALL
	Z	REF	%	W1035	105	24		SPARE	ALL
	Z	REF	%	W1035	106	24		SPARE	050-099
	Z	REF	%	W1037	083	24		SPARE	ALL
	Z	REF	%	W1037	084	24		SPARE	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 38

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0239		<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	X	<b>BACM15C3A (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
TB0239	Z	<b>BACM15C3C (continued)</b>					<b>SHELF/E08/00</b>		<b>ALL</b>
	Z	REF	%	W1037	085	24		SPARE	050-099
TB0241		<b>BACT44B0630U</b>					<b>0157/232/L032</b>		<b>ALL</b>
TB0241	X	<b>BACM15C3A</b>					<b>P001-00/ /</b>		<b>ALL</b>
TB0241	Y	<b>BACM15C3B</b>					<b>P001-00/ /</b>		<b>ALL</b>
	Y			W0011	215Z			34-22-81	ALL
	Y			W0011	216Z			34-22-81	ALL
	Y			W0011	241Z			34-22-91	ALL
	Y			W0011	248Z			34-13-11	050-099, 150-199
	Y			W0011	249Z			34-13-11	050-099, 150-199
	Y			W0011	FRM			34-22-91	ALL
	Y			W0011	FRW			34-13-11	050-099, 150-199
	Y	A003	BJ	W0011	502R	24		31-41-14	ALL
	Y	A003	BJ	W0011	507R	24		34-22-15	ALL
	Y	A003	BJ	W0031	502R	24		31-41-14	ALL
	Y	A004	BJ	W0011	502B	24		31-41-14	ALL
	Y	A004	BJ	W0011	507B	24		34-22-15	ALL
	Y	A004	BJ	W0031	502B	24		31-41-14	ALL
	X	A005	BJ	W0011	504B	24		31-41-14	ALL
	X	A005	BJ	W0031	504B	24		31-41-14	ALL
	X	A006	BJ	W0011	504R	24		31-41-14	ALL
	X	A006	BJ	W0031	504R	24		31-41-14	ALL
	Y	A007	BJ	W0011	098	24		31-51-21	ALL
	Y	A007	BJ	W0011	099	24		31-51-21	ALL
	Y	A007	BJ	W0031	097	24		31-51-21	ALL
	Y	A008	BJ	W0011	038	24		34-13-21	ALL
	Y	A008	BJ	W0011	040	24		34-13-21	ALL
	Y	A008	BJ	W0031	048	24		34-13-21	ALL
	Y	A010	BJ	W0011	720	22		34-22-81	ALL
	Y	A010	BJ	W0011	754	22		34-22-81	ALL
	Y	A010	BJ	W0011	781	22		34-22-81	ALL
	Y	A013	BJ	W0011	066	24		34-22-81	ALL
	Y	A013	BJ	W0011	610	24		34-22-81	ALL
	Y	A013	BJ	W0031	064	24		34-22-28	ALL
	Y	A013	BJ	W0031	604	24		34-22-28	ALL
	X	B005	BJ	W0011	505B	24		31-41-14	ALL
	X	B005	BJ	W0031	505B	24		31-41-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 39

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0241		<b>BACT44B0630U (continued)</b>					<b>0157/232/L032</b>		<b>ALL</b>
TB0241	X	<b>BACM15C3A (continued)</b>					<b>P001-00/ /</b>		<b>ALL</b>
TB0241	Y	<b>BACM15C3B (continued)</b>					<b>P001-00/ /</b>		<b>ALL</b>
	X	B006	BJ	W0011	505R	24		31-41-14	ALL
	X	B006	BJ	W0031	505R	24		31-41-14	ALL
	Y	C001	BJ	W0011	063	24		34-22-81	ALL
	Y	C001	BJ	W0011	064	24		34-22-18	ALL
	Y	C001	BJ	W0011	065	24		34-22-81	ALL
	Y	C001	BJ	W0011	076	24		34-22-18	ALL
	Y	C003	BJ	W0011	654	24		31-41-16	ALL
	Y	C003	BJ	W0011	658	24		31-41-16	ALL
	Y	C003	BJ	W0031	652	24		31-41-16	ALL
	Y	C004	BJ	W0011	655	24		31-41-16	ALL
	Y	C004	BJ	W0011	659	24		31-41-16	ALL
	Y	C004	BJ	W0031	653	24		31-41-16	ALL
	X	C006	BJ	W0011	FRM			34-22-91	ALL
	X	C006	BJ	W0031	209Z			34-22-92	ALL
	Y	C007	BJ	W0011	215R	24		34-22-81	ALL
	Y	C007	BJ	W0011	216R	24		34-22-81	ALL
	Y	C007	BJ	W0011	241R	24		34-22-91	ALL
	Y	C007	BJ	W0031	209R	24		34-22-92	ALL
	Y	C008	BJ	W0011	215B	24		34-22-81	ALL
	Y	C008	BJ	W0011	216B	24		34-22-81	ALL
	Y	C008	BJ	W0011	241B	24		34-22-91	ALL
	Y	C008	BJ	W0031	209B	24		34-22-92	ALL
	Y	C009	BJ	W0011	248R	24		34-13-11	ALL
	Y	C009	BJ	W0011	249R	24		34-13-11	ALL
	Y	C009	BJ	W0031	522R	24		34-13-11	ALL
	Y	C010	BJ	W0011	248B	24		34-13-11	ALL
	Y	C010	BJ	W0011	249B	24		34-13-11	ALL
	Y	C010	BJ	W0031	522B	24		34-13-11	ALL
	X	C011	BJ	W0011	FRW			34-13-11	ALL
	X	C011	BJ	W0031	522Z			34-13-11	ALL
	X	C012	BJ	W0011	214Z			34-22-81	ALL
	X	C012	BJ	W0031	523Z			34-22-81	ALL
	X	D005	BJ	W0011	007	24		34-22-81	ALL
	X	D005	BJ	W0051	008	22		34-22-81	ALL
	X	D011	BJ	W0011	214R	24		34-22-81	ALL
	X	D011	BJ	W0031	523R	24		34-22-81	ALL
	X	D012	BJ	W0011	214B	24		34-22-81	ALL
	X	D012	BJ	W0031	523B	24		34-22-81	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 40

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0241		<b>BACT44B0630U (continued)</b>					<b>0157/232/L032</b>		<b>ALL</b>
TB0241	X	<b>BACM15C3A (continued)</b>					<b>P001-00/ /</b>		<b>ALL</b>
TB0241	Y	<b>BACM15C3B (continued)</b>					<b>P001-00/ /</b>		<b>ALL</b>
	X	DED		W0011	007Z			34-22-81	ALL
	Y	DED		W0011	066Z			34-22-81	ALL
	Y	DED		W0011	610Z			34-22-81	ALL
	Y	DED		W0011	800Z			31-31-20	050-099
	Y	REF		W0011	248Z			34-13-11	275-299
	Y	REF		W0011	249Z			34-13-11	275-299
	Y	REF		W0011	FRW			34-13-11	275-299
TB0243		<b>BACT44B0630U</b>					<b>0157/232/R032</b>		<b>ALL</b>
TB0243	X	<b>BACM15C3A</b>					<b>P003-00/ /</b>		<b>ALL</b>
TB0243	Y	<b>BACM15C3B</b>					<b>P003-00/ /</b>		<b>ALL</b>
TB0243	Z	<b>BACM15C3C</b>					<b>P003-00/ /</b>		<b>ALL</b>
	Y			W0011	218Z			34-22-81	ALL
	Y			W0011	219Z			34-22-81	ALL
	Y			W0011	253Z			34-22-81	ALL
	Y			W0011	265Z			34-22-91	ALL
	Y			W0011	267Z			34-22-91	ALL
	Y			W0011	269Z			34-22-91	ALL
	Y			W0011	FRO			34-22-91	ALL
	Y			W0011	FRR			34-22-91	ALL
	Y			W0011	FRS			34-22-91	ALL
	Y	A001	BJ	W0031	229R	24		22-14-21	ALL
	Y	A001	BJ	W0031	230R	24		22-14-21	ALL
	Y	A001	BJ	W0031	231R	24		22-14-21	ALL
	Y	A002	BJ	W0031	229B	24		22-14-21	ALL
	Y	A002	BJ	W0031	230B	24		22-14-21	ALL
	Y	A002	BJ	W0031	231B	24		22-14-21	ALL
	X	A003	BJ	W0011	056	24		31-25-11	ALL
	X	A003	BJ	W0051	003	24		31-25-11	ALL
	X	A004	BJ	W0031	058	24		31-25-11	ALL
	X	A004	BJ	W0051	002	24		31-25-11	ALL
	Y	A005	BJ	W0011	231R	24		34-13-21	ALL
	Y	A005	BJ	W0031	241R	24		34-13-21	ALL
	Y	A005	BJ	W0031	242R	24		34-13-21	ALL
	Y	A006	BJ	W0011	231B	24		34-13-21	ALL
	Y	A006	BJ	W0031	241B	24		34-13-21	050-099, 157, 275-299
	Y	A006	BJ	W0031	242B	24		34-13-21	ALL
	X	A007	BJ	W0011	252R	20		34-12-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 41

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0243		<b>BACT44B0630U (continued)</b>					<b>0157/232/R032</b>		<b>ALL</b>
TB0243	X	<b>BACM15C3A (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
TB0243	Y	<b>BACM15C3B (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
TB0243	Z	<b>BACM15C3C (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
	X	A007	BJ	W0031	521R	20		34-12-21	ALL
	X	A008	BJ	W0011	252B	20		34-12-21	ALL
	X	A008	BJ	W0031	521B	20		34-12-21	ALL
	Y	A009	BJ	W0011	219R	24		34-22-81	ALL
	Y	A009	BJ	W0011	269R	24		34-22-91	ALL
	Y	A009	BJ	W0031	525R	24		34-22-91	ALL
	Y	A010	BJ	W0011	219B	24		34-22-81	ALL
	Y	A010	BJ	W0011	269B	24		34-22-91	ALL
	Y	A010	BJ	W0031	525B	24		34-22-91	ALL
	Y	A014	BJ	W0031	613	22		33-16-12	ALL
	Y	A014	BJ	W0031	790	22		33-16-16	ALL
	Y	A014	BJ	W0031	791	22		33-16-16	ALL
	Y	A015	BJ	W0051	040	24		33-13-11	ALL
	Y	A015	BJ	W0051	113	24		33-13-11	ALL
	Y	A015	BJ	W0051	116	24		33-13-17	ALL
	Y	A016	BJ	W0011	713	22		33-16-15	ALL
	Y	A016	BJ	W0011	793	22		33-16-12	ALL
	X	B003	BJ	W0011	611	24		34-22-91	ALL
	X	B003	BJ	W0031	007	24		34-22-91	050-099
	X	B003	BJ	W0031	007	22		34-22-91	150-199, 275-299
	X	B004	BJ	W0011	231Z			34-13-21	ALL
	X	B004	BJ	W0031	FRP			34-13-21	ALL
	X	B007	BJ	W0011	FRS			34-22-91	ALL
	X	B007	BJ	W0031	525Z			34-22-91	ALL
	X	B008	BJ	W0011	252Z			34-12-21	ALL
	X	B008	BJ	W0031	521Z			34-12-21	ALL
	Y	C001	BJ	W0011	709	22		33-16-15	ALL
	Y	C001	BJ	W0011	718	22		33-16-13	ALL
	Y	C001	BJ	W0051	107	22		33-16-12	ALL
	Y	C001	BJ	W0051	108	22		33-16-15	ALL
	Y	C005	BJ	W0011	253R	24		34-22-81	ALL
	Y	C005	BJ	W0011	265R	24		34-22-91	ALL
	Y	C005	BJ	W0031	249R	24		34-22-91	ALL
	Y	C006	BJ	W0011	253B	24		34-22-81	ALL
	Y	C006	BJ	W0011	265B	24		34-22-91	ALL
	Y	C006	BJ	W0031	241B	24		34-13-21	150-156, 162-199
	Y	C006	BJ	W0031	249B	24		34-22-91	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 42

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0243		<b>BACT44B0630U (continued)</b>					<b>0157/232/R032</b>		<b>ALL</b>
TB0243	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
TB0243	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
TB0243	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
	X	C008	BJ	W0011	FRR			34-22-91	ALL
	X	C008	BJ	W0031	524Z			34-22-91	ALL
	Y	C009	BJ	W0011	218R	24		34-22-81	ALL
	Y	C009	BJ	W0011	267R	24		34-22-91	ALL
	Y	C009	BJ	W0031	524R	24		34-22-91	ALL
	Y	C010	BJ	W0011	218B	24		34-22-81	ALL
	Y	C010	BJ	W0011	267B	24		34-22-91	ALL
	Y	C010	BJ	W0031	524B	24		34-22-91	ALL
	Y	C015	BJ	W0031	780	24		33-13-17	ALL
	Y	C015	BJ	W0051	114	24		33-13-17	ALL
	Y	C015	BJ	W0051	115	24		33-13-17	ALL
	Y	C016	BJ	W0011	087	22		33-16-13	ALL
	Y	C016	BJ	W0011	791	22		33-16-12	ALL
	Y	C016	BJ	W0011	805	22		33-16-15	ALL
	Y	C016	BJ	W0031	085	22		33-16-15	ALL
	X	D003	BJ	W0011	01J	22		34-12-61	ALL
	X	D003	BJ	W0051	161	22		34-12-61	ALL
	X	D004	BJ	W0011	FRO			34-22-91	ALL
	X	D004	BJ	W0031	249Z			34-22-91	ALL
	X	DED		W0011	01JZ			34-12-61	ALL
	Y	DED		W0011	087Z			33-16-13	ALL
	X	DED		W0011	611Z			34-22-91	ALL
	Y	DED		W0011	709Z			33-16-15	ALL
	Y	DED		W0011	718Z			33-16-13	ALL
	Y	DED		W0011	791Z			33-16-12	ALL
	Y	DED		W0031	085Z			33-16-15	ALL
	Y	DED		W0031	613Z			33-16-12	ALL
	Y	DED		W0031	790Z			33-16-16	ALL
	Y	DED		W0031	791Z			33-16-16	ALL
	Y	DED		W0051	107Z			33-16-12	ALL
	Y	DED		W0051	108Z			33-16-15	ALL
	Y	REF		W0031	229Z			22-14-21	ALL
	Y	REF		W0031	230Z			22-14-21	ALL
	Y	REF		W0031	231Z			22-14-21	ALL
	Y	REF		W0031	241Z			34-13-21	ALL
	Y	REF		W0031	242Z			34-13-21	ALL
	Y	REF		W0031	FRP			34-13-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 43

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0245</b>		<b>BACT44B0630U</b>					<b>0157/232/L032</b>		<b>ALL</b>
<b>TB0245</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P001-00/ /</b>		<b>ALL</b>
<b>TB0245</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P001-00/ /</b>		<b>ALL</b>
	Z	1	BJ	W0011	228R	24		22-14-11	ALL
	Z	1	BJ	W0011	229R	24		22-14-11	ALL
	Z	1	BJ	W0011	230R	24		22-14-11	ALL
	Z	1	BJ	W0011	800R	24		31-31-20	ALL
	Z	2	BJ	W0011	228B	24		22-14-11	ALL
	Z	2	BJ	W0011	229B	24		22-14-11	ALL
	Z	2	BJ	W0011	230B	24		22-14-11	ALL
	Z	2	BJ	W0011	800B	24		31-31-20	ALL
	Z	5	BJ	W0011	096	22		33-16-16	ALL
	Z	5	BJ	W0011	708	22		33-16-15	ALL
	Z	5	BJ	W0051	096	22		33-16-12	ALL
	Z	5	BJ	W0051	098	22		33-16-13	ALL
	Z	5	BJ	W0051	101	22		33-16-15	ALL
	Z	5	BJ	W0051	104	22		33-16-16	ALL
	Z	5	BJ	W0051	105	22		33-16-16	ALL
	Y	A003	BJ	W0011	095	22		33-16-16	ALL
	Y	A003	BJ	W0051	094	22		33-16-12	ALL
	Y	A003	BJ	W0051	097	22		33-16-13	ALL
	Y	A004	BJ	W0051	095	22		33-16-12	ALL
	Y	A004	BJ	W0051	102	22		33-16-15	ALL
	Y	A004	BJ	W0051	106	22		33-16-16	ALL
	Y	DED		W0011	095Z			33-16-16	ALL
	Z	DED		W0011	096Z			33-16-16	ALL
	Z	DED		W0011	708Z			33-16-15	ALL
	Z	REF		W0011	228Z			22-14-11	ALL
	Z	REF		W0011	229Z			22-14-11	ALL
	Z	REF		W0011	230Z			22-14-11	ALL
	Z	REF		W0011	800Z			31-31-20	150-199, 275-299
<b>TB0247</b>		<b>BACT44B0630U</b>					<b>0157/232/R032</b>		<b>ALL</b>
<b>TB0247</b>	<b>X</b>	<b>BACM15C3A</b>					<b>0158/212/R033</b>		<b>ALL</b>
<b>TB0247</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P003-00/ /</b>		<b>ALL</b>
<b>TB0247</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P003-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W0031	010	22		33-16-15	ALL
	Z	10	BJ	W0031	607	22		33-16-13	ALL
	Z	10	BJ	W0031	611	22		33-16-15	ALL
	Z	10	BJ	W0031	614	22		33-16-16	ALL
	Z	10	BJ	W0031	616	22		33-16-16	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 44

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0247		<b>BACT44B0630U (continued)</b>					<b>0157/232/R032</b>		<b>ALL</b>
TB0247	X	<b>BACM15C3A (continued)</b>					<b>0158/212/R033</b>		<b>ALL</b>
TB0247	Y	<b>BACM15C3B (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
TB0247	Z	<b>BACM15C3C (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W0031	617	22		33-16-16	ALL
	Z	10	BJ	W0031	789	22		33-16-12	ALL
	Z	11	BJ	W0011	792	22		33-16-12	ALL
	Z	11	BJ	W0011	795	22		33-16-16	ALL
	Z	14	BJ	W0011	122	24		33-13-11	ALL
	Z	14	BJ	W0011	194	24		33-13-18	ALL
	Z	14	BJ	W0051	047	24		33-13-11	ALL
	Z	14	BJ	W0051	053	24		33-13-11	ALL
	Z	14	BJ	W0051	057	24		33-13-11	ALL
	Z	14	BJ	W0051	124	24		33-13-11	ALL
	Z	9	BJ	W0011	088	22		33-16-13	ALL
	Z	9	BJ	W0011	094	22		33-16-16	ALL
	Z	9	BJ	W0011	167	22		33-16-13	ALL
	Z	9	BJ	W0011	717	22		33-16-15	ALL
	Z	9	BJ	W0011	794	22		33-16-12	ALL
	Z	9	BJ	W0011	796	22		33-16-16	ALL
	Z	9	BJ	W0031	086	22		33-16-15	ALL
	Y	A001	BJ	W0011	782	20		33-13-13	ALL
	Y	A001	BJ	W0031	151	20		33-13-13	ALL
	Y	A001	BJ	W0051	075	20		33-13-13	ALL
	Y	A002	BJ	W0011	788	24		33-14-21	ALL
	Y	A002	BJ	W0011	789	24		33-14-21	ALL
	Y	A002	BJ	W0011	790	24		33-14-21	ALL
	Y	A003	BJ	W0051	015	24		33-11-11	ALL
	Y	A003	BJ	W0051	016	24		33-11-11	ALL
	Y	A003	BJ	W0051	017	24		33-11-11	ALL
	Y	A004	BJ	W0051	021	24		33-11-11	ALL
	Y	A004	BJ	W0051	022	24		33-11-11	ALL
	Y	A004	BJ	W0051	023	24		33-11-11	ALL
	X	A006	BJ	W0011	736	24		73-21-14	ALL
	X	A006	BJ	W0051	033	24		73-21-14	ALL
	X	A008	BJ	W0031	352R	24		33-13-17	ALL
	X	A008	BJ	W0051	309R	24		33-13-17	ALL
	X	B005	BJ	W0031	150	20		33-13-13	ALL
	X	B005	BJ	W0051	078	20		33-13-13	ALL
	X	B007	BJ	W0031	352B	24		33-13-17	ALL
	X	B007	BJ	W0051	309B	24		33-13-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 45

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0247		<b>BACT44B0630U (continued)</b>					<b>0157/232/R032</b>		<b>ALL</b>
TB0247	X	<b>BACM15C3A (continued)</b>					<b>0158/212/R033</b>		<b>ALL</b>
TB0247	Y	<b>BACM15C3B (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
TB0247	Z	<b>BACM15C3C (continued)</b>					<b>P003-00/ /</b>		<b>ALL</b>
	X	B008	BJ	W0031	352Y	24		33-13-17	ALL
	X	B008	BJ	W0051	309Y	24		33-13-17	ALL
	Y	C001	BJ	W0031	783	24		33-14-11	ALL
	Y	C001	BJ	W0031	784	24		33-14-11	ALL
	Y	C001	BJ	W0031	785	24		33-14-11	ALL
	Y	C004	BJ	W0031	008	22		33-16-15	ALL
	Y	C004	BJ	W0031	612	22		33-16-15	ALL
	Y	C004	BJ	W0031	788	22		33-16-12	ALL
	X	C006	BJ	W0031	152	22		33-13-13	ALL
	X	C006	BJ	W0051	072	22		33-13-13	ALL
	X	DED		W0011	736Z			73-21-14	ALL
	Y	DED		W0011	782Z			33-13-13	ALL
	Z	DED		W0011	792Z			33-16-12	ALL
	Z	DED		W0011	795Z			33-16-16	ALL
	Z	DED		W0031	086Z			33-16-15	ALL
	X	DED		W0051	072Z			33-13-13	ALL
	Y	DED		W0051	075Z			33-13-13	ALL
	X	DED		W0051	078Z			33-13-13	ALL
TB0248		<b>BACT44B0770U</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	D	<b>DIODEBLOCK-REF284T0049-</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	F	<b>BACM15C1A</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	X	<b>BACM15C3A</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	Y	<b>BACM15C3B</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	Z	<b>BACM15C3C</b>					<b>P050-00/ /</b>		<b>ALL</b>
	Y			W1078	109Z			73-21-17	275-276
	Y			W1078	544Z			73-21-17	275-276
	Y			W1078	FRY			73-21-17	275-276
	Y			W1080	159Z			73-21-17	275-276
	Y			W1080	544Z			73-21-17	275-276
	Y			W1080	FRK			73-21-17	275-276
	Z	5	BJ	W1080	168	24		73-21-17	ALL
	Z	5	BJ	W1080	186	24		73-21-17	ALL
	Z	5	BJ	W1080	438	24		73-21-12	ALL
	Z	5	BJ	W1080	544JA	24		73-21-17	ALL
	Z	5	BJ	W1080	552	24		73-21-17	ALL
	Z	5	BJ	W1080	609	24		73-21-17	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 46

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0248		<b>BACT44B0770U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
	Z	5	BJ	W1080	764	24		73-21-11	ALL
	Z	6	BJ	W1080	168Z			73-21-17	ALL
	Z	6	BJ	W1080	186Z			73-21-17	ALL
	Z	6	BJ	W1080	438Z			73-21-12	ALL
	Z	6	BJ	W1080	544Z			73-21-17	ALL
	Z	6	BJ	W1080	552Z			73-21-17	ALL
	Z	6	BJ	W1080	609Z			73-21-17	ALL
	Z	6	BJ	W1080	764Z			73-21-11	ALL
	Z	7	BJ	W1078	139	24		73-21-12	ALL
	Z	7	BJ	W1078	149	24		73-21-17	ALL
	Z	7	BJ	W1078	163	24		73-21-17	ALL
	Z	7	BJ	W1078	535	24		73-21-17	ALL
	Z	7	BJ	W1078	544JA	24		73-21-17	ALL
	Z	7	BJ	W1078	609	24		73-21-17	ALL
	Z	7	BJ	W1078	764	24		73-21-11	ALL
	Z	8	BJ	W1078	139Z			73-21-12	ALL
	Z	8	BJ	W1078	149Z			73-21-17	ALL
	Z	8	BJ	W1078	163Z			73-21-17	ALL
	Z	8	BJ	W1078	535Z			73-21-17	ALL
	Z	8	BJ	W1078	544Z			73-21-17	ALL
	Z	8	BJ	W1078	609Z			73-21-17	ALL
	Z	8	BJ	W1078	764Z			73-21-11	ALL
	X	A001	BJ	W1078	749	24		21-58-11	ALL
	X	A001	BJ	W1080	094	24		21-58-11	ALL
	X	A002	BJ	W1078	517	24		21-58-11	ALL
	X	A002	BJ	W1114	016	24		21-58-11	ALL
	Y	A003	BJ	W1078	105	24		36-11-41	ALL
	Y	A003	BJ	W1078	136	24		36-11-41	ALL
	Y	A003	BJ	W1080	033	24		36-11-41	ALL
	Y	A004	BJ	W1080	159Z			73-21-17	050-099, 150-199, 277-299
	Y	A004	BJ	W1080	177Z			73-21-19	ALL
	Y	A004	BJ	W1080	544Z			73-21-17	050-099, 150-199, 277-299
	Y	A004	BJ	W1080	FRK			73-21-17	275-276
	Y	A009	BJ	W1080	715	22		24-51-52	275-299
	Y	A009	BJ	W1114	087	24		24-51-52	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 47

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0248		<b>BACT44B0770U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
	Y	A009	BJ	W1114	090	24		24-51-52	275-299
	Y	A010	BJ	W1078	514	24		21-24-11	050-099, 150-199
	Y	A010	BJ	W1078	515	24		21-24-11	050-099, 150-199
	Y	A010	BJ	W1080	716	22		24-51-52	275-299
	Y	A010	BJ	W1080	729	24		21-24-11	050-099, 150-199
	Y	A010	BJ	W1114	088	24		24-51-52	275-299
	Y	A010	BJ	W1114	089	24		24-51-52	275-299
	X	A011	BJ	W1078	176	24		36-11-52	ALL
	X	A011	BJ	W1080	120	24		36-11-52	ALL
	X	A012	BJ	W1078	724	24		21-58-15	ALL
	X	A012	BJ	W1080	048	24		21-58-15	ALL
	Y	A013	BJ	W1078	109	24		73-21-17	ALL
	Y	A013	BJ	W1078	124	24		73-21-19	ALL
	Y	A013	BJ	W1078	544JA	24		73-21-17	ALL
	Y	A014	BJ	W1080	706	24		30-31-21	ALL
	Y	A014	BJ	W1114	079	24		30-31-21	ALL
	Y	A014	BJ	W1114	080	24		30-31-21	ALL
	X	A015	BJ	W1080	715	22		24-51-52	050-099, 150-199
	X	A015	BJ	W1114	087	24		24-51-52	050-099, 150-199
	X	A016	BJ	W1078	161	24		73-21-18	ALL
	X	A016	BJ	W1114	101	24		73-21-18	ALL
	D	A017	2	W1078	521	24		34-46-12	ALL
	D	A018	2	W1078	198	22		27-61-11	ALL
	D	A019	2	W1078	725	24		21-25-11	ALL
	D	A020	2	W1080	712	24		21-25-11	ALL
	D	A021	2	W1080	160	24		73-21-19	ALL
	D	A022	2	W1078	780	22		73-21-19	ALL
	X	B001	BJ	W1080	010	24		31-51-41	150-199, 275-299
	X	B001	BJ	W1114	043	24		31-51-41	150-199, 275-299
	X	B002	BJ	W1078	157	22		36-11-51	ALL
	X	B002	BJ	W1114	028	22		36-11-51	ALL
	X	B011	BJ	W1078	195	24		36-11-62	ALL
	X	B011	BJ	W1080	128	24		36-11-62	ALL
	X	B012	BJ	W1080	047	22		36-11-52	ALL
	X	B012	BJ	W1114	055	22		36-11-52	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 48

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0248		<b>BACT44B0770U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
	X	B015	BJ	W1080	716	22		24-51-52	050-099, 150-199
	X	B015	BJ	W1114	088	24		24-51-52	050-099, 150-199
	X	B016	BJ	W1080	181	24		73-21-18	ALL
	X	B016	BJ	W1114	106	24		73-21-18	ALL
	X	C001	BJ	W1078	529R	22		26-18-22	150-199
	X	C001	BJ	W1080	108R	22		26-18-22	150-199
	X	C002	BJ	W1078	158	24		30-34-11	ALL
	X	C002	BJ	W1114	082	24		30-34-11	ALL
	Y	C003	BJ	W1080	159	24		73-21-17	ALL
	Y	C003	BJ	W1080	177	22		73-21-19	ALL
	Y	C003	BJ	W1080	544JA	24		73-21-17	ALL
	Y	C009	BJ	W1078	701	24		36-22-11	ALL
	Y	C009	BJ	W1080	132	22		36-22-11	ALL
	Y	C009	BJ	W1080	753	22		36-22-11	ALL
	Y	C010	BJ	W1078	621	22		21-66-11	050-099, 162-199
	Y	C010	BJ	W1078	726	24		21-25-11	ALL
	Y	C010	BJ	W1078	727	24		21-25-11	ALL
	Y	C010	BJ	W1080	713	24		21-25-11	ALL
	X	C011	BJ	W1078	728	24		21-26-11	ALL
	X	C011	BJ	W1080	066	24		21-26-11	ALL
	X	C012	BJ	W1078	778	24		73-21-15	ALL
	X	C012	BJ	W1080	778	24		73-21-15	ALL
	Y	C013	BJ	W1078	156	24		30-31-11	ALL
	Y	C013	BJ	W1114	073	24		30-31-11	ALL
	Y	C013	BJ	W1114	074	24		30-31-11	ALL
	Y	C014	BJ	W1078	109Z			73-21-17	050-099, 150-199, 277-299
	Y	C014	BJ	W1078	124Z			73-21-19	ALL
	Y	C014	BJ	W1078	544Z			73-21-17	050-099, 150-199, 277-299
	Y	C014	BJ	W1078	FRY			73-21-17	275-276
	X	C015	BJ	W1080	718	22		24-51-52	050-099, 150-199
	X	C015	BJ	W1114	089	24		24-51-52	050-099, 150-199
	X	C016	BJ	W1080	614	24		73-21-18	ALL
	X	C016	BJ	W1114	131	24		73-21-18	ALL
	D	C017	2	W1078	194	24		27-58-21	ALL
	D	C017	2	W1078	520	24		27-58-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 49

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0248		<b>BACT44B0770U (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>D</b>	<b>DIODEBLOCK-REF284T0049- (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
TB0248	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P050-00/ /</b>		<b>ALL</b>
	D	C018	2	W1078	520	24		27-58-21	ALL
	D	C019	2	W1078	726	24		21-25-11	ALL
	D	C020	2	W1080	713	24		21-25-11	ALL
	D	C021	2	W1080	161	24		73-21-19	ALL
	D	C021	2	W1080	781	24		73-21-19	ALL
	D	C022	2	W1078	123	24		73-21-19	ALL
	D	C022	2	W1078	779	22		73-21-19	ALL
	X	D001	BJ	W1078	110	24		28-22-12	ALL
	X	D001	BJ	W1114	051	24		28-22-12	ALL
	X	D002	BJ	W1080	707	24		30-34-21	ALL
	X	D002	BJ	W1114	076	24		30-34-21	ALL
	X	D011	BJ	W1078	247	24		36-11-62	ALL
	X	D011	BJ	W1080	200	24		36-11-62	ALL
	X	D015	BJ	W1080	719	22		24-51-52	050-099, 150-199
	X	D015	BJ	W1114	090	24		24-51-52	050-099, 150-199
	X	D016	BJ	W1078	618	24		73-21-18	ALL
	X	D016	BJ	W1114	132	24		73-21-18	ALL
	X	DED		W1114	043Z			31-51-41	150-199, 275-299
	Y	DED		W1114	073Z			30-31-11	ALL
	Y	DED		W1114	074Z			30-31-11	ALL
	X	DED		W1114	082Z			30-34-11	ALL
<b>TB0249</b>		<b>BACT44B0200U</b>					<b>//</b>		<b>ALL</b>
<b>TB0249</b>	<b>R</b>	<b>RESISTORBLOCK-233T2402-</b>					<b>0154/220/</b>		<b>ALL</b>
	R	A001	2	W0051	123	24		33-13-11	ALL
	R	A001	2	W0051	222R	24		33-13-11	ALL
	R	A002	2	W0051	019	24		33-13-11	ALL
	R	C001	2	W0051	222B	24		33-13-11	ALL
	R	C002	2	W0051	123	24		33-13-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 50

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0250		BACT44B0430U					P036-00/ /		ALL
TB0250	D	DIODEBLOCK-REF284T0187-					P036-00/ /		ALL
TB0250	G	BACM15C1B					P036-00/ /		ALL
TB0250	H	BACM15C2A					P036-00/ /		ALL
TB0250	X	BACM15C3A					P036-00/ /		ALL
TB0250	Y	BACM15C3B					P036-00/ /		ALL
TB0250	Z	BACM15C3C					P036-00/ /		ALL
	Y	A001	BJ	W0176	02T	24		78-36-11	ALL
	Y	A001	BJ	W0176	03S	24		78-36-11	ALL
	Y	A001	BJ	W0176	65L	24		78-36-11	ALL
	Y	A002	BJ	W0176	08G	22		73-21-19	275-299
	Y	A002	BJ	W0176	10D	22		SPARE	050-099
	Y	A002	BJ	W0176	10D	22		30-21-11	275-299
	Y	A002	BJ	W0176	839	22		30-21-11	275-299
	X	A003	BJ	W0176	08J	24		31-31-13	ALL
	X	A003	BJ	W0184	860	24		31-31-13	ALL
	X	A004	BJ	W0176	89A	24		21-58-12	ALL
	X	A004	BJ	W0184	75G	24		21-58-12	ALL
	D	A005	2	W0184	029	24		21-58-12	ALL
	D	A005	2	W0184	891	24		21-58-12	ALL
	D	A006	2	W0184	75H	24		21-58-12	ALL
	Y	A007	BJ	W0176	89E	24		21-58-12	ALL
	Y	A007	BJ	W0184	887	24		21-58-12	ALL
	Y	A008	BJ	W0176	89D	24		21-58-12	ALL
	Y	A008	BJ	W0184	882	24		21-58-12	ALL
	Y	A009	BJ	W0184	75W	24		21-58-12	ALL
	Y	A009	BJ	W0184	76A	24		21-58-12	ALL
	Y	A010	BJ	W0176	89J	24		21-58-12	ALL
	Y	A010	BJ	W0184	11E	24		21-58-12	ALL
	Y	A011	BJ	W0176	16R	24		21-61-61	050-099, 280-299
	Y	A011	BJ	W0176	17C	24		21-61-61	050-099, 280-299
	Y	A011	BJ	W0176	17D	24		21-61-61	050-099, 280-299
	X	B003	BJ	W0176	550	24		21-58-12	ALL
	X	B003	BJ	W0184	030	24		21-58-12	ALL
	X	B004	BJ	W0176	89B	24		21-58-12	ALL
	X	B004	BJ	W0184	883	24		21-58-12	ALL
	Y	C001	BJ	W0176	273	22		30-21-11	ALL
	Y	C001	BJ	W0176	275	22		30-21-11	ALL
	Y	C001	BJ	W0176	276	22		30-21-11	ALL
	Y	C001	BJ	W0176	277	22		30-21-11	ALL
	Y	C002	BJ	W0176	10D	22		SPARE	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 51

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0250		<b>BACT44B0430U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0250	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0250	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0250	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0250	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0250	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0250	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	C002	BJ	W0176	10D	22		30-21-11	275-299
	Y	C002	BJ	W0176	80W	22		30-21-11	050-099, 150-199
	Y	C002	BJ	W0176	80X	22		30-21-11	050-099, 150-199
	Y	C002	BJ	W0176	81H	24		30-21-11	050-099, 150-199
	Y	C002	BJ	W0176	823	24		30-21-11	275-299
	Y	C002	BJ	W0176	874	22		30-21-11	275-299
	Y	C002	BJ	W0176	881	22		30-21-11	275-299
	X	C003	BJ	W0176	89K	24		21-58-12	ALL
	X	C003	BJ	W0184	75K	24		21-58-12	ALL
	X	C004	BJ	W0184	75T	24		21-58-12	ALL
	X	C004	BJ	W0184	898	24		21-58-12	ALL
	D	C005	2	W0176	631	24		21-58-12	150-154, 275
	D	C005	2	W0176	75R	24		21-58-12	050-099, 155-199, 276-299
	D	C005	2	W0184	75R	24		21-58-12	ALL
	D	C006	2	W0184	75R	24		21-58-12	ALL
	Y	C007	BJ	W0176	89F	24		21-58-12	ALL
	Y	C007	BJ	W0184	889	24		21-58-12	ALL
	Y	C008	BJ	W0176	89C	24		21-58-12	ALL
	Y	C008	BJ	W0184	884	24		21-58-12	ALL
	Y	C008	BJ	W0184	897	24		21-58-12	ALL
	Y	C009	BJ	W0184	75X	24		21-58-12	ALL
	Y	C009	BJ	W0184	76B	24		21-58-12	ALL
	Y	C010	BJ	W0176	89H	24		21-58-12	ALL
	Y	C010	BJ	W0184	11F	24		21-58-12	ALL
	X	D003	BJ	W0176	89L	24		21-58-12	ALL
	X	D003	BJ	W0184	888	24		21-58-12	ALL
	X	D004	BJ	W0176	89G	24		21-58-12	ALL
	X	D004	BJ	W0184	895	24		21-58-12	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 52

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0252		BACT44B0430U					P036-00/ /		ALL
TB0252	D	DIODEBLOCK-REF284T0187-					P036-00/ /		ALL
TB0252	F	BACM15C1A					P036-00/ /		050-099, 150-199, 275-276, 280-299
TB0252	G	BACM15C1B					P036-00/ /		ALL
TB0252	Y	BACM15C3B					P036-00/ /		ALL
TB0252	Z	BACM15C3C					P036-00/ /		ALL
	Z	11	BJ	W0176	536	20		36-11-51	050-099, 150-155, 162-165, 275-276
	Z	11	BJ	W0176	71A	22		36-11-51	050-099, 150-156, 162-166, 275-276
	Z	11	BJ	W0176	71B	22		36-11-51	050-099, 150-156, 162-166, 275-276
	Z	11	BJ	W0176	71C	22		36-11-51	050-099, 150-156, 162-166, 275-276
	Z	11	BJ	W0176	71F	22		36-11-51	050-099, 150-156, 162-166, 275-276
	Z	11	BJ	W0176	71G	22		36-11-51	050-099, 150-156, 162-166, 275-276
	Z	11	BJ	W0176	71M	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	11	BJ	W0176	71P	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	12	BJ	W0176	71Y	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	12	BJ	W0176	72A	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	12	BJ	W0176	72B	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	12	BJ	W0176	72F	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	12	BJ	W0176	72N	20		36-11-61	050-099, 150-156, 162-166, 275-276
	G	3	2	W0176	07A	16		27-32-31	ALL
	G	3	2	W0176	07B	20		27-32-31	ALL
	G	3	2	W0176	07C	20		27-32-31	ALL
	G	3	2	W0176	07D	16		27-32-31	ALL
	Z	6	BJ	W0176	170	24		21-58-12	ALL
	Z	6	BJ	W0184	026	24		21-58-12	ALL
	Z	6	BJ	W0184	885	24		21-58-12	ALL
	Z	6	BJ	W0184	890	24		21-58-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 53

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0252		<b>BACT44B0430U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0252	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0252	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 150-199, 275-276, 280-299</b>
TB0252	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0252	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0252	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	6	BJ	W0184	893	24		21-58-12	ALL
	Z	7	BJ	W0176	638	24		21-58-12	ALL
	Z	7	BJ	W0184	078	24		21-58-16	ALL
	Z	7	BJ	W0184	75M	24		21-58-12	ALL
	Z	7	BJ	W0184	75S	24		21-58-12	ALL
	Z	7	BJ	W0184	894	24		21-58-12	ALL
	Z	7	BJ	W0184	896	24		21-58-12	ALL
	Y	A002	BJ	W0184	75L	24		21-58-12	ALL
	Y	A002	BJ	W0184	75U	24		21-58-12	ALL
	D	A004	2	W0176	520	24		21-58-16	ALL
	D	A005	2	W0176	19A	24		21-58-16	150-199, 275-299
	D	A008	2	W0176	19B	24		21-58-16	150-199, 275-299
	Y	A009	BJ	W0176	539	22		36-11-51	ALL
	Y	A009	BJ	W0176	71D	22		36-11-51	050-099, 150-156, 162-166, 275-276
	Y	A009	BJ	W0176	71E	20		36-11-51	ALL
	Y	A009	BJ	W0176	71L	20		36-11-51	ALL
	Y	A010	BJ	W0176	627	22		36-11-61	ALL
	Y	A010	BJ	W0176	71R	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Y	A010	BJ	W0176	71S	22		36-11-61	050-099, 275-299
	Y	A010	BJ	W0176	71S	20		36-11-61	150-199
	Y	A010	BJ	W0176	71T	22		36-11-61	ALL
	Y	C001	BJ	W0176	501	24		21-58-16	150-154, 275
	Y	C001	BJ	W0176	561	24		21-26-11	150-154, 275
	Y	C001	BJ	W0176	562	24		21-58-16	150-154, 275
	Y	C001	BJ	W0176	698	24		21-26-11	150-154, 275
	Y	C002	BJ	W0184	75J	24		21-58-12	ALL
	Y	C002	BJ	W0184	75V	24		21-58-12	ALL
	D	C004	2	W0176	534	24		21-58-16	ALL
	D	C005	2	W0176	19C	24		21-58-16	150-199, 275-299
	D	C008	2	W0176	19C	24		21-58-16	150-199, 275-299
	D	C008	2	W0176	19E	24		21-58-16	150-199, 275-299
	Y	C009	BJ	W0176	540	22		36-11-51	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 54

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0252		<b>BACT44B0430U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0252	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0252	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 150-199, 275-276, 280-299</b>
TB0252	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0252	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0252	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	C009	BJ	W0176	71H	20		36-11-51	ALL
	Y	C009	BJ	W0176	71J	22		36-11-51	050-099, 150-156, 162-166, 275-276
	Y	C009	BJ	W0176	71K	20		36-11-51	ALL
	Y	C010	BJ	W0176	626	22		36-11-61	ALL
	Y	C010	BJ	W0176	71U	22		36-11-61	ALL
	Y	C010	BJ	W0176	71V	22		36-11-61	ALL
	Y	C010	BJ	W0176	72C	22		36-11-61	050-099, 150-156, 162-166, 275-276
<b>TB0253</b>		<b>MS27212-3-3</b>					<b>1454/314/L032</b>		<b>050-099, 150-199</b>
		1	F	W0226	005	04		25-31-21	050-099, 150-199
		1	F2	W0226	009	02		25-31-21	050-099, 150-199
		1	F	W0308	004	04		25-31-31	050-099, 150-199
		2	F	W0226	006	04		25-31-21	050-099, 150-199
		2	F2	W0226	010	02		25-31-21	050-099, 150-199
		2	F	W0308	005	04		25-31-31	050-099, 150-199
		3	F	W0226	007	04		25-31-21	050-099, 150-199
		3	F2	W0226	011	02		25-31-21	050-099, 150-199
		3	F	W0308	006	04		25-31-31	050-099, 150-199
TB0254		<b>BACT44B0680U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>D</b>	<b>DIODEBLOCK-REF284T0188-</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>F</b>	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>050-099, 150-199</b>
TB0254	<b>G</b>	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>X</b>	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0254	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>Z</b>	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	G	13	2	W0192	049	20		36-11-62	050-099, 150-156, 162-166, 275-276
	G	13	2	W0192	22A	22		36-11-62	050-099, 150-156, 162-166, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 55

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0254		<b>BACT44B0680U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 150-199</b>
TB0254	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0254	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	G	13	2	W0192	26A	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	14	BJ	W0192	64R	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	14	BJ	W0192	65G	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	14	BJ	W0192	65M	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	14	BJ	W0192	65T	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	14	BJ	W0192	65V	24		36-11-62	050-099, 150-156, 162-166, 275-276
	G	16	BJ	W0192	61H	20		25-31-12	150-152
	Z	16	BJ	W0192	61H	20		25-31-12	153-154
	Z	16	BJ	W1118	106	20		25-33-11	153-154
	G	16	BJ	W1118	517	20		21-58-16	150-152
	Z	16	BJ	W1118	517	20		25-33-11	153-154
	G	16	BJ	W1118	559	20		25-31-12	150-152
	Z	16	BJ	W1118	559	20		25-33-11	153-154
	G	16	BJ	W1118	560	20		25-31-12	150-152
	Z	16	BJ	W1118	560	20		25-31-12	153-154
	Z	7	BJ	W0192	04U	24		21-61-21	ALL
	Z	7	BJ	W0192	05G	24		21-61-31	ALL
	Z	7	BJ	W0192	05K	24		21-61-31	ALL
	Z	7	BJ	W0192	077	24		21-61-51	ALL
	Z	7	BJ	W0192	08W	24		21-61-21	ALL
	Z	7	BJ	W0192	10J	24		21-61-51	ALL
	Z	7	BJ	W0192	15C	24		21-61-41	ALL
	Z	7	BJ	W0192	15D	24		21-61-41	ALL
	Z	8	BJ	W0192	06G	22		30-21-11	050-099, 150-199
	Z	8	BJ	W0192	08M	22		30-21-11	ALL
	Z	8	BJ	W0192	08N	22		30-21-11	275-299
	Z	8	BJ	W0192	79T	22		73-21-19	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 56

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0254		<b>BACT44B0680U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 150-199</b>
TB0254	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0254	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	8	BJ	W0192	80Y	22		30-21-11	050-099, 150-199
	Z	8	BJ	W0192	817	22		30-21-11	ALL
	Z	8	BJ	W0192	82F	22		30-21-11	050-099, 150-199
	Z	8	BJ	W0192	842	24		30-21-11	ALL
	Y	A001	BJ	W1118	018	22		27-81-11	ALL
	Y	A001	BJ	W1118	035	22		27-81-11	ALL
	Y	A001	BJ	W1118	039	22		27-81-11	ALL
	Y	A002	BJ	W0192	560	22		27-81-11	ALL
	Y	A002	BJ	W1118	037	22		27-81-11	ALL
	Y	A002	BJ	W1118	041	22		27-81-11	ALL
	Y	A003	BJ	W0192	06K	24		78-36-21	ALL
	Y	A003	BJ	W0192	06M	24		78-36-21	ALL
	Y	A003	BJ	W0192	83P	24		78-36-21	ALL
	Y	A004	BJ	W0192	286	22		30-21-11	ALL
	Y	A004	BJ	W0192	289	22		30-21-11	ALL
	Y	A004	BJ	W0192	290	22		30-21-11	ALL
	Y	A004	BJ	W0192	291	24		30-21-11	ALL
	Y	A005	BJ	W0192	02Z	24		21-61-31	ALL
	Y	A005	BJ	W0192	05J	24		21-61-31	ALL
	Y	A005	BJ	W0192	761	24		21-61-31	ALL
	Y	A006	BJ	W0192	515	20		25-33-11	050-099, 155-199, 277-299
	Y	A006	BJ	W1118	516	20		25-33-11	150-154, 275-276
	Y	A006	BJ	W1118	517	20		21-58-16	275-276
	Y	A006	BJ	W1118	518	20		21-58-16	150-152, 275-276
	Y	A006	BJ	W1118	518	20		25-33-11	153-154
	Y	A006	BJ	W1118	561	20		25-33-11	050-099, 155-199, 277-299
	Y	A006	BJ	W1118	562	20		25-33-11	050-099
	Y	A009	BJ	W0192	04E	24		21-58-14	050-099, 155-199, 276-299
	Y	A009	BJ	W0192	70U	24		21-58-14	050-099, 155-199, 276-299
	Y	A009	BJ	W0192	72L	24		21-58-14	050-099, 155-199, 276-299
	Y	A010	BJ	W1118	540	24		21-43-11	150-154, 275
	Y	A010	BJ	W1118	541	24		21-43-11	150-154, 275
	Y	A010	BJ	W1118	546	24		21-43-11	150-154, 275

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 57

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0254		<b>BACT44B0680U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 150-199</b>
TB0254	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>150-199, 275-299</b>
TB0254	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0254	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	D	A011	2	W0192	817	22		30-21-11	ALL
	F	A017	BJ	W0198	623	20		25-31-12	150-152
	F	A017	BJ	W1118	558	20		25-31-12	150-152
	Y	C001	BJ	W1118	016	22		27-81-11	ALL
	Y	C001	BJ	W1118	034	22		27-81-11	ALL
	Y	C001	BJ	W1118	038	22		27-81-11	ALL
	Y	C002	BJ	W1118	017	22		27-81-11	ALL
	Y	C002	BJ	W1118	036	22		27-81-11	ALL
	Y	C002	BJ	W1118	040	22		27-81-11	ALL
	Y	C003	BJ	W0192	02Y	24		21-61-21	ALL
	Y	C003	BJ	W0192	04W	24		21-61-21	ALL
	Y	C003	BJ	W0192	730	24		21-61-21	ALL
	Y	C004	BJ	W0192	13U	22		36-11-52	157, 167-199, 277-299
	Y	C004	BJ	W0192	65H	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	C004	BJ	W0192	65L	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	C004	BJ	W0192	65N	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	C004	BJ	W0192	809	22		36-11-52	157, 167-199, 277-299
	Y	C004	BJ	W0192	810	22		36-11-52	157, 167-199, 277-299
	Y	C005	BJ	W0192	81P	22		30-21-11	050-099, 150-199
	Y	C005	BJ	W0192	81R	22		30-21-11	050-099, 150-199
	Y	C005	BJ	W0192	82E	24		30-21-11	050-099, 150-199
	Y	C006	BJ	W0198	622	20		25-33-11	050-099
	Y	C006	BJ	W1118	530	20		25-33-11	275-276
	Y	C006	BJ	W1118	537	20		25-33-11	275-276
	Y	C006	BJ	W1118	563	20		25-33-11	050-099
	D	C011	2	W0192	288	22		30-21-11	ALL
	F	C017	BJ	W0198	622	20		25-31-12	150-152
	F	C017	BJ	W1118	557	20		25-31-12	150-152
	Y	DED		W0198	622Z			25-33-11	050-099

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 58

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0255</b>		<b>BACT44A0920D</b>					<b>0212/195/L045</b>		<b>ALL</b>
<b>TB0255</b>	<b>X</b>	<b>BACM15C3A</b>					<b>0212/195/L045</b>		<b>ALL</b>
<b>TB0255</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>0212/195/L045</b>		<b>ALL</b>
	X	A001	BJ	W0517	002	22		31-31-26	ALL
	X	A001	BJ	W0614	064	22		31-31-26	ALL
	Y	A003	BJ	W0517	205R	24		23-22-11	ALL
	Y	A003	BJ	W0711	214R	24		23-22-12	ALL
	Y	A003	BJ	W0847	214R	24		23-22-12	ALL
	Y	A004	BJ	W0517	205Z			23-22-11	ALL
	Y	A004	BJ	W0711	214Z			23-22-12	ALL
	Y	A004	BJ	W0847	214Z			23-22-12	ALL
	X	A005	BJ	W0517	206Z			34-61-16	ALL
	X	A005	BJ	W0711	215Z			34-61-16	ALL
	X	A006	BJ	W0519	206R	24		34-61-26	ALL
	X	A006	BJ	W0711	216R	24		34-61-26	ALL
	X	B001	BJ	W0606	102	22		31-31-26	ALL
	X	B001	BJ	W0687	002	22		31-31-26	ALL
	X	B005	BJ	W0517	206R	24		34-61-16	ALL
	X	B005	BJ	W0711	215R	24		34-61-16	ALL
	X	B006	BJ	W0519	206B	24		34-61-26	ALL
	X	B006	BJ	W0711	216B	24		34-61-26	ALL
	X	C001	BJ	W0517	001	24		34-61-16	ALL
	X	C001	BJ	W0731	001	24		34-61-16	ALL
	Y	C003	BJ	W0517	205B	24		23-22-11	ALL
	Y	C003	BJ	W0711	214B	24		23-22-12	ALL
	Y	C003	BJ	W0847	214B	24		23-22-12	ALL
	X	C005	BJ	W0517	206B	24		34-61-16	ALL
	X	C005	BJ	W0711	215B	24		34-61-16	ALL
	X	D001	BJ	W0519	001	24		34-61-26	ALL
	X	D001	BJ	W0733	001	24		34-61-26	150-199, 275-299
	X	D005	BJ	W0519	206Z			34-61-26	ALL
	X	D005	BJ	W0711	216Z			34-61-26	ALL
<b>TB0257</b>		<b>284T1329</b>					<b>SHELF/E09/01</b>		<b>156-157, 166-199, 277-299</b>
<b>TB0257</b>	<b>F</b>	<b>BACM15C1A</b>					<b>SHELF/E09/01</b>		<b>150, 153-199, 277-299</b>
<b>TB0257</b>	<b>G</b>	<b>BACM15C1B</b>					<b>SHELF/E09/01</b>		<b>150, 152-199, 277-299</b>
<b>TB0257</b>	<b>H</b>	<b>BACM15C2A</b>					<b>SHELF/E09/01</b>		<b>150, 153-199, 277-299</b>
<b>TB0257</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>SHELF/E09/01</b>		<b>280-299</b>
<b>TB0257</b>	<b>Z</b>	<b>BACM15C3B</b>					<b>SHELF/E09/01</b>		<b>277-299</b>
	H	1	2	W0091	009	16		23-25-11	156-157, 166-199, 277-299
	H	1	2	W0091	021	20		23-25-16	156-157, 166-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 59

Feb 06/2009



**767-200/300 WIRING DIAGRAM MANUAL**

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0257		<b>284T1329 (continued)</b>					<b>SHELF/E09/01</b>		<b>156-157, 166-199, 277-299</b>
TB0257	F	<b>BACM15C1A (continued)</b>					<b>SHELF/E09/01</b>		<b>150, 153-199, 277-299</b>
TB0257	G	<b>BACM15C1B (continued)</b>					<b>SHELF/E09/01</b>		<b>150, 152-199, 277-299</b>
TB0257	H	<b>BACM15C2A (continued)</b>					<b>SHELF/E09/01</b>		<b>150, 153-199, 277-299</b>
TB0257	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E09/01</b>		<b>280-299</b>
TB0257	Z	<b>BACM15C3B (continued)</b>					<b>SHELF/E09/01</b>		<b>277-299</b>
	H	1	2	W0091	022	20		23-25-16	156-157, 166-199, 277-299
	H	1	2	W0091	024	20		23-25-17	156-157, 166-199, 277-299
	H	1	2	W0091	025	20		23-25-17	156-157, 166-199, 277-299
	H	1	2	W0091	051	20		23-25-17	156-157, 166-199, 277-299
	H	1	2	W0091	052	20		23-25-17	156-157, 166-199, 277-299
	H	1	2	W0091	053	20		23-25-12	277-299
	H	1	2	W9026	009	16		23-25-11	150, 153-155, 162-165
	H	1	2	W9026	022	20		23-25-16	150, 153-155, 162-165
	H	1	2	W9026	024	20		23-25-17	150, 153-155, 162-165
	H	1	2	W9026	025	20		23-25-17	150, 153-155, 162-165
	H	1	2	W9026	051	20		23-25-17	150, 153-155, 162-165
	H	1	2	W9026	052	20		23-25-17	150, 153-155, 162-165
	G	11	2	W0091	234R	24		23-25-13	156-157, 166-199, 277-299
	G	11	2	W0091	235R	24		23-25-13	156-157, 166-199, 277-299
	G	11	2	W0091	243R	24		23-25-15	167-199
	G	11	2	W0095	205R	24		23-25-13	156-157, 166-199, 277-299
	G	11	2	W9026	234R	22		23-25-13	150, 153-155, 162-165
	G	11	2	W9026	235R	22		23-25-13	150, 153-155, 162-165
	G	11	2	W9026	907R	22		23-25-13	150, 153-155, 162-165
	G	12	2	W0091	234B	24		23-25-13	156-157, 166-199, 277-299
	G	12	2	W0091	235B	24		23-25-13	156-157, 166-199, 277-299
	G	12	2	W0091	243B	24		23-25-15	167-199
	G	12	2	W0095	205B	24		23-25-13	156-157, 166-199, 277-299
	G	12	2	W9026	234B	22		23-25-13	150, 153-155, 162-165
	G	12	2	W9026	235B	22		23-25-13	150, 153-155, 162-165
	G	12	2	W9026	907B	22		23-25-13	150, 153-155, 162-165
	G	13	2	W0091	232R	24		23-25-13	167-199
	G	13	2	W0091	241R	24		23-25-13	167-199
	G	13	2	W0091	242R	24		23-25-15	167-199
	G	14	2	W0091	232B	24		23-25-13	167-199
	G	14	2	W0091	241B	24		23-25-13	167-199
	G	14	2	W0091	242B	24		23-25-15	167-199
	H	2	2	W9026	053	20		23-25-12	150, 153-155, 162-165
	G	20	2	W9026	903	22		23-32-21	150, 152-199
	G	20	2	W9026	944	22		23-32-21	150, 152-199

**TERMINAL STRIP LIST**

D280T132

**91-21-41**

Section TB0200

Page 60

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0257		<b>284T1329 (continued)</b>					<b>SHELF/E09/01</b>		<b>156-157, 166-199, 277-299</b>
TB0257	F	<b>BACM15C1A (continued)</b>					<b>SHELF/E09/01</b>		<b>150, 153-199, 277-299</b>
TB0257	G	<b>BACM15C1B (continued)</b>					<b>SHELF/E09/01</b>		<b>150, 152-199, 277-299</b>
TB0257	H	<b>BACM15C2A (continued)</b>					<b>SHELF/E09/01</b>		<b>150, 153-199, 277-299</b>
TB0257	Y	<b>BACM15C3B (continued)</b>					<b>SHELF/E09/01</b>		<b>280-299</b>
TB0257	Z	<b>BACM15C3B (continued)</b>					<b>SHELF/E09/01</b>		<b>277-299</b>
	G	27	2	W0091	220R	24		23-25-17	156-157, 166-199, 277-299
	G	27	2	W0091	226R	24		23-25-17	156-157, 166-199, 277-299
	G	27	2	W0091	240R	24		23-25-17	156-157, 166-199, 277-299
	G	27	2	W9026	220R	22		23-25-17	150, 153-155, 162-165
	G	27	2	W9026	226R	22		23-25-17	150, 153-155, 162-165
	G	27	2	W9026	240R	22		23-25-17	150, 153-155, 162-165
	G	29	2	W0091	220B	24		23-25-17	156-157, 166-199, 277-299
	G	29	2	W0091	226B	24		23-25-17	156-157, 166-199, 277-299
	G	29	2	W0091	240B	24		23-25-17	156-157, 166-199, 277-299
	G	29	2	W9026	220B	22		23-25-17	150, 153-155, 162-165
	G	29	2	W9026	226B	22		23-25-17	150, 153-155, 162-165
	G	29	2	W9026	240B	22		23-25-17	150, 153-155, 162-165
	H	3	2	W0091	001	16		23-25-11	156-157, 166-199, 277-299
	H	3	2	W0091	002	20		23-25-11	156-157, 166-199, 277-299
	H	3	2	W0091	007	20		23-25-11	167-199, 277-299
	H	3	2	W0091	008	20		23-25-11	167-199, 277-299
	H	3	2	W0091	009	16		23-25-11	277-299
	H	3	2	W0091	053	20		23-25-12	156-157, 166-199
	H	3	2	W0091	068	20		23-25-15	167-199
	H	3	2	W0091	939	20		23-25-13	156-157, 166-199
	H	3	2	W9026	001	16		23-25-11	150, 153-155, 162-165
	H	3	2	W9026	002	20		23-25-11	150, 153-155, 162-165
	H	3	2	W9026	939	20		23-25-13	150, 153-155, 162-165
	G	31	2	W0091	218R	24		23-25-17	156-157, 166-199, 277-299
	G	31	2	W0091	228R	24		23-25-17	156-157, 166-199, 277-299
	G	31	2	W0091	238R	24		23-25-17	156-157, 166-199, 277-299
	G	31	2	W9026	218R	22		23-25-17	150, 153-155, 162-165
	G	31	2	W9026	228R	22		23-25-17	150, 153-155, 162-165
	G	31	2	W9026	238R	22		23-25-17	150, 153-155, 162-165
	G	33	2	W0091	218B	24		23-25-17	156-157, 166-199, 277-299
	G	33	2	W0091	228B	24		23-25-17	156-157, 166-199, 277-299
	G	33	2	W0091	238B	24		23-25-17	156-157, 166-199, 277-299
	G	33	2	W9026	218B	22		23-25-17	150, 153-155, 162-165
	G	33	2	W9026	228B	22		23-25-17	150, 153-155, 162-165
	G	33	2	W9026	238B	22		23-25-17	150, 153-155, 162-165

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 61

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0257		284T1329 (continued)					SHELF/E09/01		156-157, 166-199, 277-299
TB0257	F	BACM15C1A (continued)					SHELF/E09/01		150, 153-199, 277-299
TB0257	G	BACM15C1B (continued)					SHELF/E09/01		150, 152-199, 277-299
TB0257	H	BACM15C2A (continued)					SHELF/E09/01		150, 153-199, 277-299
TB0257	Y	BACM15C3B (continued)					SHELF/E09/01		280-299
TB0257	Z	BACM15C3B (continued)					SHELF/E09/01		277-299
	G	34	2	W0091	219R	24		23-25-17	156-157, 166-199, 277-299
	G	34	2	W0091	227R	24		23-25-17	156-157, 166-199, 277-299
	G	34	2	W0091	239R	24		23-25-17	156-157, 166-199, 277-299
	G	34	2	W9026	219R	22		23-25-17	150, 153-155, 162-165
	G	34	2	W9026	227R	22		23-25-17	150, 153-155, 162-165
	G	34	2	W9026	239R	22		23-25-17	150, 153-155, 162-165
	G	35	2	W0091	219B	24		23-25-17	156-157, 166-199, 277-299
	G	35	2	W0091	227B	24		23-25-17	156-157, 166-199, 277-299
	G	35	2	W0091	239B	24		23-25-17	156-157, 166-199, 277-299
	G	35	2	W9026	219B	22		23-25-17	150, 153-155, 162-165
	G	35	2	W9026	227B	22		23-25-17	150, 153-155, 162-165
	G	35	2	W9026	239B	22		23-25-17	150, 153-155, 162-165
	H	5	2	W0091	201R	24		23-25-11	156-157, 166, 277-299
	H	5	#	W0091	201R	24		23-25-11	167-199
	H	5	2	W0091	203R	24		23-25-11	277-299
	H	5	2	W0091	204R	24		23-25-11	156-157, 166-199, 277-299
	H	5	2	W0091	216R	24		23-25-16	156-157, 166-199, 277-299
	H	5	2	W0091	221R	24		23-25-17	156-157, 166-199, 277-299
	H	5	2	W0091	225R	24		23-25-17	156-157, 166-199, 277-299
	H	5	2	W0091	248R	24		23-25-16	167-199
	H	5	2	W0095	201R	24		23-25-11	156-157, 166, 277-299
	H	5	#	W0095	201R	24		23-25-11	167-199
	H	5	2	W9026	204R	22		23-25-16	150, 153-155, 162-165
	H	5	2	W9026	216R	24		23-25-16	150, 153-155, 162-165
	H	5	2	W9026	221R	22		23-25-17	150, 153-155, 162-165
	H	5	2	W9026	225R	22		23-25-17	150, 153-155, 162-165
	H	7	2	W0091	201B	24		23-25-11	156-157, 166, 277-299
	H	7	#	W0091	201B	24		23-25-11	167-199
	H	7	2	W0091	203B	24		23-25-11	277-299
	H	7	2	W0091	204B	24		23-25-11	156-157, 166-199, 277-299
	H	7	2	W0091	216B	24		23-25-16	156-157, 166-199, 277-299
	H	7	2	W0091	221B	24		23-25-17	156-157, 166-199, 277-299
	H	7	2	W0091	225B	24		23-25-17	156-157, 166-199, 277-299
	H	7	2	W0091	248B	24		23-25-16	167-199
	H	7	2	W0095	201B	24		23-25-11	156-157, 166, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 62

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0257		284T1329 (continued)					SHELF/E09/01		156-157, 166-199, 277-299
TB0257	F	BACM15C1A (continued)					SHELF/E09/01		150, 153-199, 277-299
TB0257	G	BACM15C1B (continued)					SHELF/E09/01		150, 152-199, 277-299
TB0257	H	BACM15C2A (continued)					SHELF/E09/01		150, 153-199, 277-299
TB0257	Y	BACM15C3B (continued)					SHELF/E09/01		280-299
TB0257	Z	BACM15C3B (continued)					SHELF/E09/01		277-299
	H	7	#	W0095	201B	24		23-25-11	167-199
	H	7	2	W9026	204B	22		23-25-16	150, 153-155, 162-165
	H	7	2	W9026	216B	24		23-25-16	150, 153-155, 162-165
	H	7	2	W9026	221B	22		23-25-17	150, 153-155, 162-165
	H	7	2	W9026	225B	22		23-25-17	150, 153-155, 162-165
	H	9	2	W0091	920	20		23-25-13	156-157, 166-199
	H	9	2	W0091	922	20		23-25-13	156-157, 166-199
	H	9	2	W0091	938	20		23-25-13	156-157, 166-199
	H	9	2	W9026	920	20		23-25-13	150, 153-155, 162-165
	H	9	2	W9026	922	20		23-25-13	150, 153-155, 162-165
	H	9	2	W9026	938	20		23-25-13	150, 153-155, 162-165
	F	A015	2	W0091	236R	24		23-25-13	156-157, 166-199, 277-299
	F	A015	2	W0095	206R	24		23-25-13	156-157, 166-199, 277-299
	F	A019	2	W0091	237R	24		23-25-13	277-299
	F	A019	2	W0095	207R	24		23-25-13	156-157, 166-199, 277-299
	F	A021	2	W0091	016Z			23-25-14	156-157, 166-199, 277-299
	F	A021	2	W0095	001Z			23-25-14	156-157, 166-199, 277-299
	F	A023	2	W0091	017Z			23-25-14	156-157, 166-199, 277-299
	F	A023	2	W0095	002Z			23-25-14	156-157, 166-199, 277-299
	F	A025	2	W0091	018	24		23-25-14	156-157, 166-199, 277-299
	F	A025	2	W0095	003	24		23-25-14	156-157, 166-199, 277-299
	F	C015	2	W0091	236B	24		23-25-13	156-157, 166-199, 277-299
	F	C015	2	W0095	206B	24		23-25-13	156-157, 166-199, 277-299
	F	C019	2	W0091	237B	24		23-25-13	277-299
	F	C019	2	W0095	207B	24		23-25-13	156-157, 166-199, 277-299
	F	C021	2	W0091	016	24		23-25-14	156-157, 166-199, 277-299
	F	C021	2	W0095	001	24		23-25-14	156-157, 166-199, 277-299
	F	C023	2	W0091	017	24		23-25-14	156-157, 166-199, 277-299
	F	C023	2	W0095	002	24		23-25-14	156-157, 166-199, 277-299
	F	C025	2	W0091	019	24		23-25-14	156-157, 166-199, 277-299
	F	C025	2	W0095	004	24		23-25-14	156-157, 166-199, 277-299
	H	CAP	Y	W0091	069	20		23-25-16	167-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 63

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0258</b>		<b>BACT44B0310U</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0258</b>	<b>D</b>	<b>DIODEBLOCK-REF284T3601-</b>					<b>P036-00/ /</b>		<b>275-299</b>
<b>TB0258</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>155-199, 277-299</b>
	D	A005	2	W0176	85T	22		74-31-11	275-299
	D	A006	2	W0176	08G	22		73-21-19	275-299
	D	C005	2	W0176	85K	22		73-21-19	275-299
	D	C006	2	W0176	85K	22		73-21-19	275-299
	D	C006	2	W0184	08D	22		73-21-19	275-299
<b>TB0260</b>		<b>BACT44B0310U</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0260</b>	<b>D</b>	<b>DIODEBLOCK-REF284T0187-</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0260</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0260</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0260</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0260</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
<b>TB0260</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z	2	BJ	W0176	501	24		21-58-16	050-099, 155-199, 276-299
	Z	2	BJ	W0176	561	24		21-26-11	050-099, 155-199, 276-299
	Z	2	BJ	W0176	562	24		21-58-16	050-099, 155-199, 276-299
	Z	2	BJ	W0176	698	24		21-26-11	050-099, 155-199, 276-299
	Z	2	BJ	W0176	75S	24		21-58-12	050-099, 155-199, 276-299
	Z	3	BJ	W0176	71M	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	3	BJ	W0176	71N	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	3	BJ	W0176	71W	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	3	BJ	W0176	71X	22		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	3	BJ	W0176	92D	24		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	3	BJ	W0176	92R	24		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	3	BJ	W0176	92X	24		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	3	BJ	W0176	93B	24		36-11-61	050-099, 150-156, 162-166, 275-276
	Z	4	BJ	W0176	802	24		36-11-61	150-154, 275
	Z	4	BJ	W0176	86F	24		36-11-61	150-154, 275
	Z	4	BJ	W0176	92T	24		36-11-61	150-154, 275
	Y	A005	BJ	W0176	530	24		36-11-61	150-154, 275

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 64

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0260		<b>BACT44B0310U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0260	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0260	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0260	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0260	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0260	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0260	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	A005	BJ	W0176	802	24		36-11-61	050-099, 155-156, 162-166, 276
	Y	A005	BJ	W0176	86F	24		36-11-61	050-099, 155-156, 162-166, 276
	Y	A005	BJ	W0176	92T	24		36-11-61	050-099, 155-156, 162-166, 276
	Y	A005	BJ	W0176	93D	24		36-11-61	150-154, 275
	Y	A005	BJ	W0176	93F	24		SPARE	150-154
	Y	A005	BJ	W0176	93F	24		36-11-61	275
	Y	A005	BJ	W0176	93G	24		36-11-61	275
	Y	A006	BJ	W0176	530	24		36-11-61	157, 167-199, 277-299
	Y	A006	BJ	W0176	92S	24		36-11-61	050-099, 150-156, 162-166, 275-276
	Y	A006	BJ	W0176	92V	24		36-11-61	050-099, 150-156, 162-166, 275-276
	Y	A006	BJ	W0176	92Y	24		36-11-61	050-099, 150-156, 162-166, 275-276
	Y	A006	BJ	W0176	93D	24		36-11-61	157, 167-199, 277-299
	Y	A006	BJ	W0176	93G	24		36-11-61	157, 167-199, 277-299
	D	A007	2	W0176	09Y	24		21-45-21	ALL
	D	A007	2	W0176	10B	24		21-45-21	ALL
	D	A008	2	W0176	86F	24		36-11-61	050-099, 150-156, 162-166, 275-276
	Y	C005	BJ	W0176	92C	24		36-11-61	150-154, 275
	Y	C005	BJ	W0176	92W	24		36-11-61	150-154, 275
	D	C007	2	W0176	10A	24		21-45-21	ALL
	D	C008	2	W0176	47F	22		36-11-61	050-099, 150-156, 162-166, 275-276
	D	C008	2	W0176	93E	24		36-11-61	050-099, 150-156, 162-166, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 65

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0262		BACT44B0310U					P037-00/ /		ALL
TB0262	D	DIODEBLOCK-REF284T0188-					P037-00/ /		050-099, 150-199
TB0262	G	BACM15C1B					P037-00/ /		ALL
TB0262	Y	BACM15C3B					P037-00/ /		ALL
TB0262	Z	BACM15C3C					P037-00/ /		ALL
	G	1	2	W0198	576R	20		26-23-12	155-199, 275-299
	G	1	2	W0198	577R	20		26-23-12	155-199, 275-299
	G	1	2	W0198	579R	20		26-23-12	155-199, 275-299
	G	2	2	W0198	580R	20		26-23-12	155-199, 275-299
	G	2	2	W0198	583R	20		26-23-12	155-199, 275-299
	G	2	2	W0198	584R	20		26-23-12	155-199, 275-299
	Z	5	BJ	W0192	846R	20		26-23-12	155-199, 275-299
	Z	5	BJ	W0198	600R	20		26-23-12	155-199, 275-299
	Z	5	BJ	W0198	605R	20		26-23-12	155-199, 275-299
	Z	5	BJ	W0198	606R	20		26-23-12	155-199, 275-299
	Z	5	BJ	W0198	619R	20		26-23-12	155-199, 275-299
	Z	7	BJ	W0198	574R	20		26-23-12	150-199, 275-299
	Z	7	BJ	W0198	575R	20		26-23-12	150-199, 275-299
	Z	7	BJ	W0198	581R	20		26-23-12	150-199, 275-299
	Z	7	BJ	W0198	582R	20		26-23-12	150-199, 275-299
	Z	7	BJ	W0198	598R	20		26-23-12	150-199, 275-299
	Z	8	BJ	W0192	847R	20		26-23-12	155-199, 275-299
	Z	8	BJ	W0198	601R	20		26-23-12	155-199, 275-299
	Z	8	BJ	W0198	607R	20		26-23-12	155-199, 275-299
	Z	8	BJ	W0198	608R	20		26-23-12	155-199, 275-299
	Z	8	BJ	W0198	621R	20		26-23-12	155-199, 275-299
	D	A001	2	W0198	579R	20		26-23-12	150-154
	D	A002	2	W0198	580R	20		26-23-12	150-154
	Y	A003	BJ	W0192	844R	20		26-23-12	150-199, 275-299
	Y	A003	BJ	W0198	580R	20		26-23-12	050-099
	Y	A003	BJ	W0198	586R	20		26-23-12	150-199, 275-299
	Y	A003	BJ	W0198	593R	20		26-23-12	050-099
	Y	A003	BJ	W0198	594R	20		26-23-12	150-199, 275-299
	Y	A003	BJ	W0198	609R	20		26-23-12	050-099
	Y	A004	BJ	W0198	588R	20		26-23-12	150-199, 275-299
	Y	A004	BJ	W0198	591R	20		26-23-12	150-199, 275-299
	Y	A004	BJ	W0198	596R	20		26-23-12	150-199, 275-299
	Y	A005	BJ	W0192	847R	20		26-23-12	150-154
	Y	A005	BJ	W0198	601R	20		26-23-12	150-154
	Y	A005	BJ	W0198	607R	20		26-23-12	150-154
	Y	A005	BJ	W0198	608R	20		26-23-12	150-154

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 66

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0262		<b>BACT44B0310U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0262	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 150-199</b>
TB0262	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0262	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0262	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	D	C001	2	W0198	576R	20		26-23-12	150-154
	D	C001	2	W0198	577R	20		26-23-12	150-154
	D	C002	2	W0198	583R	20		26-23-12	150-154
	D	C002	2	W0198	584R	20		26-23-12	150-154
	Y	C003	BJ	W0192	845R	20		26-23-12	150-199, 275-299
	Y	C003	BJ	W0198	579R	20		26-23-12	050-099
	Y	C003	BJ	W0198	590R	20		26-23-12	150-199, 275-299
	Y	C003	BJ	W0198	592R	20		26-23-12	050-099
	Y	C003	BJ	W0198	595R	20		26-23-12	150-199, 275-299
	Y	C003	BJ	W0198	610R	20		26-23-12	050-099
	Y	C004	BJ	W0192	846R	20		26-23-12	150-154
	Y	C004	BJ	W0198	600R	20		26-23-12	150-154
	Y	C004	BJ	W0198	605R	20		26-23-12	150-154
	Y	C004	BJ	W0198	606R	20		26-23-12	150-154
TB0264		<b>BACT44B0310U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0264	<b>D</b>	<b>DIODEBLOCK-REF284T0188-</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0264	<b>F</b>	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0264	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
	D	A001	2	W0192	17Y	24		21-58-12	ALL
	D	A002	2	W0192	19G	24		21-58-12	ALL
	D	A003	2	W0192	19H	24		21-58-12	050-099, 150-199, 275-276
	D	A003	2	W0192	74R	22		21-66-21	050-099, 162-199
	D	A004	2	W0192	19H	24		21-58-12	050-099, 150-199, 275-276
	D	A004	2	W0192	31G	22		21-66-41	150, 152-157
	D	A004	2	W0192	73X	22		21-66-11	050-099, 162-199
	D	A008	2	W0192	19L	24		21-45-21	ALL
	D	C001	2	W0192	17R	24		21-58-12	050-099, 150-199, 275-276
	D	C001	2	W0192	17X	24		21-58-12	ALL
	D	C001	2	W0192	19M	24		21-45-21	277-299
	D	C002	2	W0192	17S	24		21-58-12	050-099, 150-199, 275-276
	D	C002	2	W0192	19F	24		21-58-12	ALL
	D	C002	2	W0192	19N	24		21-45-21	277-299
	D	C003	2	W0192	17S	24		21-58-12	050-099, 150-199, 275-276
	D	C003	2	W0192	19N	24		21-45-21	050-099, 150-199, 275-276
	D	C004	2	W0192	17R	24		21-58-12	050-099, 150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 67

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity	
		Term					CO			
TB0264		<b>BACT44B0310U (continued)</b>						<b>P037-00/ /</b>		<b>ALL</b>
TB0264	D	<b>DIODEBLOCK-REF284T0188- (continued)</b>						<b>P037-00/ /</b>		<b>ALL</b>
TB0264	F	<b>BACM15C1A (continued)</b>						<b>P037-00/ /</b>		<b>ALL</b>
TB0264	Y	<b>BACM15C3B (continued)</b>						<b>P037-00/ /</b>		<b>ALL</b>
	D	C004	2	W0192	19M	24		21-45-21	050-099, 150-199, 275-276	
	D	C008	2	W0192	19P	24		21-45-21	ALL	
TB0266		<b>BACT44B1948U</b>						<b>P033-00/ /</b>		<b>ALL</b>
TB0266	D	<b>DIODEBLOCK-REF284T0189-</b>						<b>P033-00/ /</b>		<b>050-099, 155-199</b>
TB0266	D	<b>DIODEBLOCK-REF284T0187-</b>						<b>P033-00/ /</b>		<b>150-154</b>
TB0266	R	<b>RESISTORBLOCK-REF284T0189-</b>						<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0266	X	<b>BACM15C3A</b>						<b>P033-00/ /</b>		<b>ALL</b>
TB0266	Y	<b>BACM15C3B</b>						<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0266	Z	<b>BACM15C3C</b>						<b>P033-00/ /</b>		<b>050-099, 150-199</b>
	X			W0142	11XZ			78-34-11	ALL	
	X			W0142	11YZ			78-34-11	ALL	
	X			W0142	FRA			78-34-11	ALL	
	X			W0144	825Z			78-34-11	ALL	
	X			W0144	826Z			78-34-11	ALL	
	X			W0144	FRB			78-34-11	ALL	
	Z	11	BJ	W0142	40M	22		30-81-11	050-099, 150-199	
	Z	11	BJ	W0142	41F	22		30-81-11	050-099, 150-199	
	Z	11	BJ	W0142	41G	22		30-81-11	050-099, 150-199	
	Z	11	BJ	W0144	20G	22		30-81-11	050-099, 150-199	
	Z	11	BJ	W0144	20H	22		30-81-11	050-099, 150-199	
	Z	12	BJ	W0142	80B	20		30-81-11	050-099, 150-199	
	Z	12	BJ	W0144	60A	22		30-81-11	050-099, 150-199	
	D	A001	2	W0142	42N	22		30-11-11	050-099, 150-199	
	D	A002	2	W0142	40A	22		30-81-11	050-099, 150-199	
	D	A003	2	W0142	40N	20		30-81-11	050-099, 150-199	
	D	A004	2	W0142	40L	22		30-81-11	050-099, 150-199	
	D	A005	2	W0142	40K	22		30-81-11	050-099, 150-199	
	D	A006	2	W0142	40B	22		30-81-11	050-099, 150-199	
	D	A007	2	W0142	40L	22		30-81-11	050-099, 150-199	
	D	A007	2	W0142	40M	22		30-81-11	050-099, 150-199	
	D	A008	2	W0142	40J	22		30-81-11	050-099, 150-199	
	D	A008	2	W0142	40K	22		30-81-11	050-099, 150-199	
	X	A009	BJ	W0052	088	24		21-26-11	156-157, 166-199, 277-299	
	X	A009	BJ	W0142	01J	24		21-26-11	156-157, 166-199, 277-299	
	X	A010	BJ	W0142	40S	22		30-81-11	050-099, 150-199	
	X	A010	BJ	W0144	20F	22		30-81-11	050-099, 150-199	

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 68

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0266		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0266	<b>D</b>	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 155-199</b>
TB0266	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P033-00/ /</b>		<b>150-154</b>
TB0266	<b>R</b>	<b>RESISTORBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0266	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0266	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0266	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
	D	A013	2	W0144	21A	20		30-21-11	050-099, 150-199
	D	A014	2	W0142	42R	20		30-21-11	050-099, 150-199
	Y	A015	BJ	W0142	41D	22		30-81-11	050-099, 150-199
	Y	A015	BJ	W0142	42W	22		30-81-11	050-099, 150-199
	Y	A015	BJ	W0142	42X	22		30-81-11	050-099, 150-199
	Y	A016	BJ	W0144	20L	22		30-81-11	050-099, 150-199
	Y	A016	BJ	W0144	20R	22		30-81-11	050-099, 150-199
	Y	A016	BJ	W0144	20W	22		30-81-11	050-099, 150-199
	R	A017	2	W0144	50A	22		30-81-11	050-099, 150-199
	R	A018	2	W0142	50H	22		30-81-11	050-099, 150-199
	Y	A019	BJ	W0142	50E	22		30-81-11	050-099, 150-199
	Y	A019	BJ	W0142	50F	22		30-81-11	050-099, 150-199
	Y	A019	BJ	W0142	50G	22		30-81-11	050-099, 150-199
	Y	A019	BJ	W0144	20K	22		30-81-11	050-099, 150-199
	X	B009	BJ	W0142	FRA			78-34-11	ALL
	X	B009	BJ	W0144	FRB			78-34-11	ALL
	X	B010	BJ	W0142	40R	22		30-81-11	050-099, 150-199
	X	B010	BJ	W0144	20E	22		30-81-11	050-099, 150-199
	D	C001	2	W0142	609	22		30-11-11	050-099, 150-199
	D	C002	2	W0144	20C	22		30-81-11	050-099, 150-199
	D	C002	2	W0144	50A	22		30-81-11	050-099, 150-199
	D	C003	2	W0142	40T	22		30-81-11	050-099, 150-199
	D	C004	2	W0142	40E	22		30-81-11	050-099, 150-199
	D	C004	2	W0142	43R	20		30-21-11	050-099, 150-199
	D	C005	2	W0142	40C	22		30-81-11	050-099, 150-199
	D	C005	2	W0142	40D	22		30-81-11	050-099, 150-199
	D	C006	2	W0142	40C	22		30-81-11	050-099, 150-199
	D	C006	2	W0142	50H	22		30-81-11	050-099, 150-199
	D	C007	2	W0144	20D	22		30-81-11	050-099, 150-199
	D	C007	2	W0144	22A	20		30-21-11	050-099, 150-199
	D	C008	2	W0144	20B	22		30-81-11	050-099, 150-199
	D	C008	2	W0144	20C	22		30-81-11	050-099, 150-199
	X	C009	BJ	W0142	11X	20		78-34-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 69

Feb 06/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0266		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0266	D	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 155-199</b>
TB0266	D	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P033-00/ /</b>		<b>150-154</b>
TB0266	R	<b>RESISTORBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0266	X	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0266	Y	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
TB0266	Z	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
	X	C009	BJ	W0144	825	20		78-34-11	ALL
	X	C010	BJ	W0142	41L	22		30-81-11	050-099, 150-199
	X	C010	BJ	W0144	20P	22		30-81-11	050-099, 150-199
	D	C013	2	W0144	22A	20		30-21-11	050-099, 150-199
	D	C014	2	W0142	43R	20		30-21-11	050-099, 150-199
	Y	C016	BJ	W0142	40T	22		30-81-11	050-099, 150-199
	Y	C016	BJ	W0142	41U	22		30-81-11	050-099, 150-199
	Y	C016	BJ	W0144	20S	22		30-81-11	050-099, 150-199
	R	C017	2	W0142	50F	22		30-81-11	050-099, 150-199
	R	C018	2	W0142	50E	22		30-81-11	050-099, 150-199
	X	D009	BJ	W0142	11Y	20		78-34-11	ALL
	X	D009	BJ	W0144	826	20		78-34-11	ALL
	X	D010	BJ	W0142	41K	22		30-81-11	050-099, 150-199
	X	D010	BJ	W0144	20M	22		30-81-11	050-099, 150-199
<b>TB0268</b>		<b>BACT44B1948U</b>					<b>P033-00/ /</b>		<b>ALL</b>
<b>TB0268</b>	D	<b>DIODEBLOCK-REF286T0189-</b>					<b>P033-00/ /</b>		<b>ALL</b>
<b>TB0268</b>	G	<b>BACM15C1B</b>					<b>P033-00/ /</b>		<b>ALL</b>
<b>TB0268</b>	X	<b>BACM15C3A</b>					<b>P033-00/ /</b>		<b>ALL</b>
<b>TB0268</b>	Y	<b>BACM15C3B</b>					<b>P033-00/ /</b>		<b>ALL</b>
<b>TB0268</b>	Z	<b>BACM15C3C</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
	Z	4	BJ	W0142	40N	20		30-81-11	050-099, 150-199
	Z	4	BJ	W0142	41E	22		30-81-11	050-099, 150-199
	Z	4	BJ	W0142	41J	22		30-81-11	050-099, 150-199
	Z	4	BJ	W0142	42A	22		30-11-11	050-099, 150-199
	Z	4	BJ	W0142	42D	22		30-11-11	050-099, 150-199
	Z	4	BJ	W0142	42F	22		30-11-11	050-099, 150-199
	Z	4	BJ	W0142	42K	22		30-11-11	050-099, 150-199
	Z	4	BJ	W0142	50G	22		30-81-11	050-099, 150-199
	G	7	2	W0144	101	20		30-71-21	050-099, 150-199
	G	7	2	W0144	101	22		30-71-21	275-299
	G	7	2	W0144	102	20		30-71-21	050-099, 155-199
	G	7	2	W0144	102	22		30-71-21	150-154, 275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 70

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0268		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>D</b>	<b>DIODEBLOCK-REF286T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
	G	7	2	W0144	103	20		30-71-21	050-099, 155-199
	G	7	2	W0144	103	22		30-71-21	150-154, 275-299
	G	7	2	W0144	106	20		30-71-21	050-099
	X	A001	BJ	W0144	100	24		27-58-11	ALL
	X	A001	BJ	W0144	A-A			27-58-11	ALL
	X	A002	BJ	W0144	765	24		27-58-11	ALL
	X	A002	BJ	W0144	A-C			27-58-11	ALL
	Y	A005	BJ	W0142	10L	22		28-22-31	ALL
	Y	A005	BJ	W0144	647	22		28-22-31	ALL
	Y	A005	BJ	W0144	655	22		28-22-31	ALL
	Y	A006	BJ	W0142	42A	22		30-11-11	050-099, 150-199
	Y	A006	BJ	W0142	586	22		30-11-11	ALL
	Y	A006	BJ	W0142	604	22		30-11-11	ALL
	Y	A006	BJ	W0142	605	22		30-11-11	050-099, 150-199
	Y	A006	BJ	W0142	864	22		30-11-11	275-299
	Y	A008	BJ	W0142	40J	22		30-81-11	050-099, 150-199
	Y	A008	BJ	W0142	41B	22		30-81-11	050-099, 150-199
	Y	A008	BJ	W0142	41C	22		30-81-11	050-099, 150-199
	Y	A009	BJ	W0142	40A	22		30-81-11	050-099, 150-199
	Y	A009	BJ	W0142	40B	22		30-81-11	050-099, 150-199
	Y	A009	BJ	W0142	42G	22		30-11-11	050-099, 150-199
	Y	A009	BJ	W0142	42N	22		30-11-11	050-099, 150-199
	D	A010	2	W0142	41W	22		30-81-11	050-099, 150-199
	D	A011	2	W0144	20X	22		30-81-11	050-099, 150-199
	D	A012	2	W0142	41X	22		30-81-11	050-099, 150-199
	X	B001	BJ	W0144	096	24		27-58-11	ALL
	X	B001	BJ	W0144	A-B			27-58-11	ALL
	X	B002	BJ	W0144	766	24		27-58-11	ALL
	X	B002	BJ	W0144	A-G			27-58-11	ALL
	X	C001	BJ	W0144	094	24		27-58-11	ALL
	X	C001	BJ	W0144	A-E			27-58-11	ALL
	X	C002	BJ	W0142	10S	22		28-22-31	ALL
	X	C002	BJ	W0144	651	22		28-22-31	ALL
	Y	C006	BJ	W0142	095	22		30-11-11	ALL
	Y	C006	BJ	W0142	600	22		30-11-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 71

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0268		<b>BACT44B1948U (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>D</b>	<b>DIODEBLOCK-REF286T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0268	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>050-099, 150-199</b>
	Y	C006	BJ	W0142	606	22		30-11-11	275-299
	Y	C006	BJ	W0142	700	22		30-11-11	ALL
	Y	C008	BJ	W0142	42H	22		30-11-11	050-099, 150-199
	Y	C008	BJ	W0142	42L	22		30-11-11	050-099, 150-199
	Y	C008	BJ	W0142	42M	22		30-11-11	050-099, 150-199
	Y	C009	BJ	W0142	10M	22		28-22-31	ALL
	Y	C009	BJ	W0144	648	22		28-22-31	ALL
	Y	C009	BJ	W0144	656	22		28-22-31	ALL
	D	C010	2	W0142	41N	22		30-81-11	050-099, 150-199
	D	C011	2	W0144	20U	22		30-81-11	050-099, 150-199
	D	C012	2	W0142	41R	22		30-81-11	050-099, 150-199
	X	D001	BJ	W0144	097	24		27-58-11	ALL
	X	D001	BJ	W0144	A-F			27-58-11	ALL
	X	D002	BJ	W0142	10T	22		28-22-31	ALL
	X	D002	BJ	W0144	658	22		28-22-31	ALL
	Y	DED		W0142	10LZ			28-22-31	ALL
	Y	DED		W0142	10MZ			28-22-31	ALL
	X	DED		W0142	10SZ			28-22-31	ALL
	X	DED		W0142	10TZ			28-22-31	ALL
	Y	DED		W0144	647Z			28-22-31	ALL
	Y	DED		W0144	648Z			28-22-31	ALL
	X	DED		W0144	651Z			28-22-31	ALL
	Y	DED		W0144	655Z			28-22-31	ALL
	Y	DED		W0144	656Z			28-22-31	ALL
	X	DED		W0144	658Z			28-22-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 72

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0272		BACT44B0910U					P036-00/ /		ALL
TB0272	D	DIODEBLOCK-REF284T0187-					P036-00/ /		ALL
TB0272	F	BACM15C1A					P036-00/ /		ALL
TB0272	G	BACM15C1B					P036-00/ /		ALL
TB0272	H	BACM15C2A					P036-00/ /		ALL
TB0272	R	RESISTORBLOCK					P036-00/ /		ALL
TB0272	X	BACM15C3A					P036-00/ /		ALL
TB0272	Y	BACM15C3B					P036-00/ /		ALL
TB0272	Z	BACM15C3C					P036-00/ /		ALL
	H	10	2	W0176	825	22		28-41-12	ALL
	H	10	2	W0184	111	18		28-21-11	ALL
	H	10	2	W0184	112	18		28-21-11	ALL
	H	10	2	W0184	113	22		28-21-12	ALL
	H	10	2	W0184	114	22		28-21-12	ALL
	H	10	2	W0184	115	22		28-21-12	ALL
	Z	16	BJ	W0176	20D	24		21-58-16	ALL
	Z	16	BJ	W0176	72J	24		21-58-16	050-099, 155-199, 276-299
	Z	16	BJ	W0180	010	24		21-58-16	ALL
	Z	16	BJ	W0184	084	24		21-58-16	ALL
	Z	16	BJ	W0184	853	24		21-58-16	ALL
	Z	17	BJ	W0176	11R	24		21-61-71	ALL
	Z	17	BJ	W0176	16C	24		21-61-71	ALL
	Z	17	BJ	W0176	16D	24		21-61-61	ALL
	Z	17	BJ	W0176	16H	24		21-61-61	ALL
	Z	17	BJ	W0176	288	24		21-61-21	ALL
	G	30	2	W0180	098	18		32-71-11	150-199, 275-299
	G	30	2	W0184	184	18		32-71-11	150-199, 275-299
	G	30	2	W0184	186	24		32-71-11	150-199, 275-299
	G	42	2	W0176	530	24		36-11-61	050-099, 155-156, 162-166, 276
	G	42	2	W0176	93D	24		36-11-61	050-099, 155-156, 162-166
	G	42	2	W0176	93G	24		36-11-61	050-099, 150-156, 162-166, 276
	G	7	2	W0176	795	18		28-41-12	ALL
	G	7	2	W0184	600	18		28-41-12	ALL
	G	7	2	W0184	603	18		28-41-12	ALL
	G	8	2	W0176	827	18		28-41-12	ALL
	G	8	2	W0180	055	22		28-41-12	ALL
	G	8	2	W0180	056	22		28-41-22	ALL
	G	8	2	W0180	057	22		28-41-23	ALL
	G	9	2	W0176	767	22		28-41-21	ALL
	G	9	2	W0176	826	18		28-41-12	ALL
	G	9	2	W0184	838	22		28-41-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 73

Feb 06/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0272		BACT44B0910U (continued)					P036-00/ /		ALL
TB0272	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		ALL
TB0272	F	BACM15C1A (continued)					P036-00/ /		ALL
TB0272	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0272	H	BACM15C2A (continued)					P036-00/ /		ALL
TB0272	R	RESISTORBLOCK (continued)					P036-00/ /		ALL
TB0272	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0272	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0272	Z	BACM15C3C (continued)					P036-00/ /		ALL
	X	A001	BJ	W0176	05C	24		24-51-71	ALL
	X	A001	BJ	W0180	119	24		24-51-71	ALL
	X	A002	BJ	W0176	224Z			32-42-11	ALL
	X	A002	BJ	W0180	202Z			32-42-11	ALL
	X	A003	BJ	W0176	05G	24		28-25-11	ALL
	X	A003	BJ	W0184	821	24		28-25-11	ALL
	X	A004	BJ	W0176	05S	24		32-42-11	ALL
	X	A004	BJ	W0184	796	24		32-42-11	ALL
	Y	A005	BJ	W0176	245R	24		28-41-11	ALL
	Y	A005	BJ	W0184	085	24		28-41-11	ALL
	Y	A005	BJ	W0184	204R	24		28-41-11	ALL
	Y	A006	BJ	W0176	13X	24		21-61-71	ALL
	Y	A006	BJ	W0176	15S	24		21-61-71	ALL
	Y	A006	BJ	W0176	15U	24		21-61-71	ALL
	F	A012	2	W0176	879	20		25-31-21	050-099, 150-199
	F	A012	2	W0176	879	18		25-31-21	275-299
	F	A012	2	W0180	105	18		25-31-21	ALL
	X	A013	BJ	W0056	062	22		21-45-21	050-099, 150-156, 162-166, 275-276
	X	A013	BJ	W0056	062	20		21-45-21	157, 167-199, 277-299
	X	A013	BJ	W0176	09P	22		21-45-21	050-099, 150-156, 162-166, 275-276
	X	A013	BJ	W0176	09P	20		21-45-21	157, 167-199, 277-299
	F	A015	2	W0176	51N	24		21-58-12	ALL
	F	A015	2	W0184	11B	24		21-58-12	ALL
	X	A018	BJ	W0176	889	24		32-42-11	275-299
	X	A018	BJ	W0184	829	22		32-42-11	275-299
	F	A019	2	W0182	135	18		21-24-11	050-099, 150-199
	F	A019	2	W0184	715	18		21-24-11	050-099, 150-199
	D	A020	2	W0176	15R	24		21-61-71	150-199
	D	A020	2	W0176	15S	24		21-61-71	150-199

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 74

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0272		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	D	A021	2	W0184	845	24		21-58-16	ALL
	D	A021	2	W0184	850	24		21-58-16	ALL
	D	A022	2	W0176	632	24		36-11-41	ALL
	Y	A023	BJ	W0176	16R	24		21-61-61	150-199, 275-278
	Y	A023	BJ	W0176	17C	24		21-61-61	150-199, 275-278
	Y	A023	BJ	W0176	17D	24		21-61-61	150-199, 275-278
	Y	A024	BJ	W0176	639	24		21-58-12	ALL
	Y	A024	BJ	W0184	75C	24		21-58-12	ALL
	Y	A024	BJ	W0184	892	24		21-58-12	ALL
	Y	A025	BJ	W0176	285R	24		77-12-11	150-157, 275-276
	Y	A025	BJ	W0176	287R	24		77-12-11	150-157, 275-276
	Y	A026	BJ	W0176	285B	24		77-12-11	150-157, 275-276
	Y	A026	BJ	W0176	287B	24		77-12-11	150-157, 275-276
	F	A027	2	W0176	01V	18		25-31-31	277-299
	F	A027	2	W0180	107	18		25-31-31	277-299
	F	A028	2	W0176	042	18		32-71-11	150-199, 275-299
	F	A028	2	W0184	183	18		32-71-11	150-199, 275-299
	F	A029	2	W0176	040	24		32-71-11	150-199, 275-299
	F	A029	2	W0184	187	24		32-71-11	150-199, 275-299
	Y	A031	BJ	W0176	16M	24		21-61-61	ALL
	Y	A031	BJ	W0176	16N	24		21-61-61	ALL
	Y	A031	BJ	W0176	17E	24		21-61-61	ALL
	Y	A031	BJ	W0176	17H	24		21-61-61	ALL
	Y	A032	BJ	W0184	11A	24		21-58-12	ALL
	Y	A032	BJ	W0184	11D	24		21-58-12	ALL
	Y	A032	BJ	W0184	11F	24		21-58-12	ALL
	D	A033	2	W0176	17B	24		21-61-61	ALL
	D	A033	2	W0176	17C	24		21-61-61	ALL
	D	A034	2	W0184	182	20		76-11-11	ALL
	D	A035	2	W0184	703	24		29-11-32	ALL
	D	A036	2	W0184	704	24		29-11-32	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 75

Feb 06/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0272		BACT44B0910U (continued)					P036-00/ /		ALL
TB0272	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		ALL
TB0272	F	BACM15C1A (continued)					P036-00/ /		ALL
TB0272	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0272	H	BACM15C2A (continued)					P036-00/ /		ALL
TB0272	R	RESISTORBLOCK (continued)					P036-00/ /		ALL
TB0272	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0272	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0272	Z	BACM15C3C (continued)					P036-00/ /		ALL
	D	A037	2	W0176	15R	24		21-61-71	050-099, 275-299
	D	A037	2	W0176	15S	24		21-61-71	050-099, 275-299
	D	A038	2	W0184	824	20		29-11-32	ALL
	D	A039	2	W0184	783	22		32-42-11	ALL
	D	A039	2	W0184	784	22		32-42-11	ALL
	D	A040	2	W0184	517	22		29-11-32	ALL
	D	A041	2	W0184	792	22		32-42-11	ALL
	X	B001	BJ	W0176	817	22		78-36-11	ALL
	X	B001	BJ	W0176	818	22		78-36-11	ALL
	X	B002	BJ	W0176	05E	24		24-51-71	ALL
	X	B002	BJ	W0180	113	24		24-51-71	ALL
	X	B003	BJ	W0176	245B	24		28-41-11	ALL
	X	B003	BJ	W0184	204B	24		28-41-11	ALL
	X	B004	BJ	W0176	05T	24		32-42-11	ALL
	X	B004	BJ	W0184	797	24		32-42-11	ALL
	X	B013	BJ	W0056	063	22		21-45-21	050-099, 150-156, 162-166, 275-276
	X	B013	BJ	W0056	063	20		21-45-21	157, 167-199, 277-299
	X	B013	BJ	W0176	09Q	22		21-45-21	050-099, 150-156, 162-166, 275-276
	X	B013	BJ	W0176	09Q	20		21-45-21	157, 167-199, 277-299
	X	C001	BJ	W0176	224B	24		32-42-11	ALL
	X	C001	BJ	W0180	202B	24		32-42-11	ALL
	X	C002	BJ	W0176	889	24		32-42-11	150-199
	X	C002	BJ	W0184	829	22		32-42-11	150-199
	X	C003	BJ	W0176	05Q	24		32-42-11	ALL
	X	C003	BJ	W0184	794	24		32-42-11	ALL
	X	C004	BJ	W0176	05U	24		32-42-11	ALL
	X	C004	BJ	W0184	799	24		32-42-11	ALL
	Y	C005	BJ	W0176	91L	24		76-11-11	050-099
	Y	C005	BJ	W0176	91L	22		76-11-11	150-199, 275-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 76

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0272		<b>BACT44B0910U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0272	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	C005	BJ	W0184	91M	20		76-11-11	ALL
	Y	C005	BJ	W0184	91N	20		76-11-11	ALL
	Y	C006	BJ	W0176	17U	22		78-36-11	150-199
	Y	C006	BJ	W0176	808	22		78-36-11	ALL
	Y	C006	BJ	W0176	810	22		78-36-11	ALL
	Y	C006	BJ	W0176	831	22		78-36-11	050-099, 275-299
	Y	C006	BJ	W0176	837	22		78-36-11	ALL
	F	C012	2	W0176	880	20		25-31-21	050-099, 150-199
	F	C012	2	W0176	880	18		25-31-21	275-299
	F	C012	2	W0180	104	18		25-31-21	ALL
	X	C014	BJ	W0176	19J	22		32-45-11	050-099, 151-199
	X	C014	BJ	W0184	50R	22		32-45-11	050-099, 150-199
	F	C015	2	W0176	51M	24		21-58-12	ALL
	F	C015	2	W0184	774	24		21-58-12	ALL
	F	C018	2	W0176	889	24		32-42-11	050-099
	F	C018	2	W0184	829	22		32-42-11	050-099
	F	C019	2	W0182	136	18		21-24-11	050-099, 150-199
	F	C019	2	W0184	716	18		21-24-11	050-099, 150-199
	D	C020	2	W0176	15P	24		21-61-71	150-199
	D	C020	2	W0176	16C	24		21-61-71	150-199
	D	C021	2	W0184	853	24		21-58-16	ALL
	D	C022	2	W0176	09B	24		36-11-41	ALL
	Y	C023	BJ	W0176	175	24		21-58-12	ALL
	Y	C023	BJ	W0184	032	24		21-58-12	ALL
	Y	C023	BJ	W0184	886	24		21-58-12	ALL
	Y	C024	BJ	W0184	75A	24		21-58-12	ALL
	Y	C024	BJ	W0184	75E	24		21-58-12	ALL
	Y	C024	BJ	W0184	75Y	24		21-58-12	ALL
	Y	C025	BJ	W0176	285Z			77-12-11	150-157, 275-276
	Y	C025	BJ	W0176	287Z			77-12-11	150-157, 275-276
	Y	C026	BJ	W0176	19J	22		32-45-11	150

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 77

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0272		BACT44B0910U (continued)					P036-00/ /		ALL
TB0272	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		ALL
TB0272	F	BACM15C1A (continued)					P036-00/ /		ALL
TB0272	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0272	H	BACM15C2A (continued)					P036-00/ /		ALL
TB0272	R	RESISTORBLOCK (continued)					P036-00/ /		ALL
TB0272	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0272	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0272	Z	BACM15C3C (continued)					P036-00/ /		ALL
	F	C027	2	W0176	01U	18		25-31-31	277-299
	F	C027	2	W0180	106	18		25-31-31	277-299
	F	C028	2	W0176	041	18		32-71-11	150-199, 275-299
	F	C028	2	W0184	185	18		32-71-11	150-199, 275-299
	Y	C031	BJ	W0176	11X	24		21-61-71	050-099, 275-299
	Y	C031	BJ	W0176	12X	24		21-61-71	050-099, 275-299
	Y	C031	BJ	W0176	12Y	24		21-61-71	050-099, 275-299
	Y	C031	BJ	W0176	13W	24		21-61-71	050-099, 275-299
	Y	C032	BJ	W0176	51L	24		21-58-12	ALL
	Y	C032	BJ	W0184	11G	24		21-58-12	ALL
	Y	C032	BJ	W0184	881	24		21-58-12	ALL
	D	C033	2	W0176	16D	24		21-61-61	ALL
	D	C033	2	W0176	17A	24		21-61-61	ALL
	D	C034	2	W0184	173	20		76-11-11	ALL
	D	C035	2	W0184	149	22		27-09-13	ALL
	D	C035	2	W0184	836	24		29-11-32	ALL
	D	C036	2	W0184	165	22		27-09-13	ALL
	D	C036	2	W0184	835	24		29-11-32	ALL
	D	C037	2	W0176	15P	24		21-61-71	050-099, 275-299
	D	C037	2	W0176	16C	24		21-61-71	050-099, 275-299
	D	C038	2	W0184	673	22		29-11-32	ALL
	D	C038	2	W0184	823	22		29-11-32	ALL
	D	C039	2	W0184	786	22		32-42-11	ALL
	D	C040	2	W0184	701	24		29-11-32	ALL
	D	C041	2	W0176	05M	22		32-42-11	ALL
	D	C042	2	W0176	93D	24		36-11-61	276
	D	CAP	Y	W0176	93F	24		SPARE	150-154
	D	CAP	Y	W0176	93F	24		36-11-61	275
	D	CAP	Y	W0176	93P	24		36-11-61	150-154
	D	CAP	Y	W0176	93P	24		SPARE	275
	Y	CAP	Y	W0184	218B	24		77-12-11	150-155, 275-276

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 78

Feb 06/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0272		BACT44B0910U (continued)					P036-00/ /		ALL
TB0272	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		ALL
TB0272	F	BACM15C1A (continued)					P036-00/ /		ALL
TB0272	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0272	H	BACM15C2A (continued)					P036-00/ /		ALL
TB0272	R	RESISTORBLOCK (continued)					P036-00/ /		ALL
TB0272	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0272	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0272	Z	BACM15C3C (continued)					P036-00/ /		ALL
	Y	CAP	Y	W0184	218B	24		77-12-11	156-157
	Y	CAP	Y	W0184	218R	24		77-12-11	150-155, 275-276
	Y	CAP	Y	W0184	218R	24		77-12-11	156-157
	X	D001	BJ	W0176	224R	24		32-42-11	ALL
	X	D001	BJ	W0180	202R	24		32-42-11	ALL
	X	D002	BJ	W0176	05F	24		28-25-11	ALL
	X	D002	BJ	W0184	610	24		28-25-11	ALL
	X	D003	BJ	W0176	05R	24		32-42-11	ALL
	X	D003	BJ	W0184	793	24		32-42-11	ALL
	X	D004	BJ	W0176	05V	24		32-42-11	ALL
	X	D004	BJ	W0184	801	24		32-42-11	ALL
	X	DED		W0176	05FZ			28-25-11	ALL
	X	DED		W0176	05GZ			28-25-11	ALL
	G	DED		W0176	767Z			28-41-21	ALL
	G	DED		W0176	795Z			28-41-12	ALL
	X	DED		W0176	818Z			78-36-11	ALL
	G	DED		W0176	826Z			28-41-12	ALL
	G	DED		W0176	827Z			28-41-12	ALL
	F	DED		W0180	104Z			25-31-21	ALL
	F	DED		W0180	105Z			25-31-21	ALL
	F	DED		W0180	106Z			25-31-31	277-299
	F	DED		W0180	107Z			25-31-31	277-299
	Y	DED		W0184	218Z			77-12-11	150-157, 275-276

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 79

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0274		BACT44B0910U					P037-00/ /		ALL
TB0274	D	DIODEBLOCK-REF284T0188-					P037-00/ /		ALL
TB0274	F	BACM15C1A					P037-00/ /		ALL
TB0274	G	BACM15C1B					P037-00/ /		ALL
TB0274	X	BACM15C3A					P037-00/ /		ALL
TB0274	Y	BACM15C3B					P037-00/ /		ALL
TB0274	Z	BACM15C3C					P037-00/ /		ALL
	G	42	2	W0192	061	24		36-11-62	050-099, 155-156, 162-166, 276
	G	42	2	W0192	65U	24		36-11-62	050-099, 155-156, 162-166, 276
	G	42	2	W0192	65Y	24		36-11-62	050-099, 155-156, 162-166, 276
	G	5	2	W1118	003	18		27-81-21	ALL
	G	5	2	W1118	014	18		27-81-21	ALL
	G	5	2	W1118	044	18		27-81-21	ALL
	G	6	2	W1118	004	18		27-81-21	ALL
	G	6	2	W1118	013	18		27-81-21	ALL
	G	6	2	W1118	043	18		27-81-21	ALL
	G	7	2	W1118	005	18		27-81-21	ALL
	G	7	2	W1118	009	18		27-81-21	ALL
	G	7	2	W1118	042	18		27-81-21	ALL
	G	8	2	W0192	573	18		27-81-21	ALL
	G	8	2	W0192	578	18		27-81-21	ALL
	G	8	2	W0192	815	18		27-81-21	ALL
	G	9	2	W0192	844	22		78-36-21	ALL
	G	9	2	W0192	847	22		78-36-21	ALL
	G	9	2	W0192	850	22		78-36-21	ALL
	G	9	2	W0192	851	22		78-36-21	ALL
	Y	A003	BJ	W0192	06R	24		78-36-21	ALL
	Y	A003	BJ	W0192	189	24		78-34-21	ALL
	Y	A003	BJ	W0192	87B	20		78-34-21	ALL
	Y	A004	BJ	W0192	78B	20		78-34-21	ALL
	Y	A004	BJ	W0192	84S	20		78-34-21	ALL
	Y	A004	BJ	W0198	634	20		78-34-21	ALL
	Y	A010	BJ	W0192	613	20		33-42-11	ALL
	Y	A010	BJ	W0192	614	20		33-42-11	ALL
	Y	A010	BJ	W0192	831	20		33-42-11	ALL
	Y	A011	BJ	W0188	111	22		78-36-11	ALL
	Y	A011	BJ	W0188	112	22		78-36-11	ALL
	Y	A011	BJ	W0192	06U	22		78-36-21	ALL
	X	A012	BJ	W0058	035	22		21-26-21	ALL
	X	A012	BJ	W1118	073	22		21-26-21	ALL
	X	A013	BJ	W0188	002	22		78-36-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 80

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0274		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	A013	BJ	W0192	853	22		78-36-21	ALL
	D	A014	2	W0188	111	22		78-36-11	ALL
	D	A015	2	W0192	06U	22		78-36-21	ALL
	D	A016	2	W0198	560	22		26-16-21	ALL
	D	A016	2	W0198	561	22		26-16-21	ALL
	D	A017	2	W0198	561	22		26-16-21	ALL
	D	A018	2	W0192	716	22		29-11-12	ALL
	D	A019	2	W0198	093	24		28-25-11	ALL
	D	A020	2	W0188	126	24		29-11-12	ALL
	D	A020	2	W0192	794	24		29-11-12	ALL
	D	A021	2	W0188	127	24		29-11-22	ALL
	D	A022	2	W0198	155	22		49-61-11	ALL
	D	A023	2	W0192	897	22		36-11-52	ALL
	D	A024	2	W0198	533R	22		26-15-12	ALL
	D	A024	2	W0198	536R	22		26-15-12	ALL
	D	A025	2	W0192	889	22		29-11-12	ALL
	D	A026	2	W0192	109	24		29-11-12	ALL
	Y	A029	BJ	W0192	06E	22		73-21-19	ALL
	Y	A029	BJ	W0192	06H	22		73-21-19	ALL
	Y	A029	%	W0192	07C	22		73-21-19	275-299
	Y	A029	BJ	W0192	88X	22		73-21-19	050-099, 150-199
	D	A031	2	W0192	621	24		36-11-41	ALL
	F	A032	2	W0192	13N	24		36-11-41	ALL
	F	A032	2	W0198	197	24		36-11-41	ALL
	Y	A033	BJ	W0192	13R	24		36-11-41	ALL
	Y	A033	BJ	W0192	13X	24		36-11-41	ALL
	Y	A033	BJ	W0192	617	24		36-11-41	ALL
	Y	A034	BJ	W0188	136	24		36-11-41	ALL
	Y	A034	BJ	W0192	13S	24		36-11-41	ALL
	Y	A034	BJ	W0192	13T	24		36-11-41	ALL
	D	A035	2	W0198	137	20		76-11-11	ALL
	D	A036	2	W0192	79T	22		73-21-19	275-299
	D	A037	2	W0192	89C	22		74-31-21	275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 81

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0274		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	D	A038	2	W0198	180	16		27-09-13	ALL
	Y	A039	BJ	W0192	238R	24		32-42-11	ALL
	Y	A039	BJ	W0192	248R	24		27-32-21	ALL
	Y	A039	BJ	W0192	292R	24		32-42-11	ALL
	Y	A039	BJ	W0192	901R	24		34-53-21	275-299
	Y	A040	BJ	W0192	238Z			32-42-11	ALL
	Y	A040	BJ	W0192	248Z			27-32-21	ALL
	Y	A040	BJ	W0192	292Z			32-42-11	ALL
	Y	A040	BJ	W0192	901Z			34-53-21	275-299
	D	A041	2	W0192	20B	20		29-11-14	ALL
	X	B012	BJ	W0058	033	22		21-26-21	ALL
	X	B012	BJ	W1118	071	22		21-26-21	ALL
	X	B013	BJ	W0188	11H	22		32-45-11	275-299
	X	B013	BJ	W0192	22S	22		32-45-11	ALL
	X	B013	BJ	W0198	11B	22		32-45-11	050-099, 150-199
	D	C002	2	W0192	66A	24		SPARE	150-154, 275-276
	Y	C003	BJ	W0192	814	22		27-81-21	ALL
	Y	C003	BJ	W1118	002	22		27-81-21	ALL
	Y	C003	BJ	W1118	015	22		27-81-21	ALL
	Y	C004	BJ	W0192	91L	24		76-11-11	050-099
	Y	C004	BJ	W0192	91L	22		76-11-11	275-299
	Y	C004	BJ	W0198	91M	20		76-11-11	050-099, 275-299
	Y	C004	BJ	W0198	91N	20		76-11-11	050-099, 275-299
	Y	C010	BJ	W0192	660	24		21-26-21	ALL
	Y	C010	BJ	W0192	664	24		21-26-21	ALL
	Y	C010	BJ	W1118	074	24		21-26-21	ALL
	Y	C010	BJ	W1118	545	24		21-44-21	ALL
	Y	C011	BJ	W0188	124	24		36-11-41	ALL
	Y	C011	BJ	W0192	66A	24		SPARE	050-099, 150-156, 162-166, 275-276
	Y	C011	BJ	W0192	803	24		36-11-52	ALL
	Y	C011	BJ	W0192	812	24		36-11-52	ALL
	X	C012	BJ	W0188	018	24		21-58-14	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 82

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0274		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	C012	BJ	W0192	04G	24		21-58-14	150-154, 275
	X	C012	BJ	W0192	72N	24		21-58-14	050-099, 155-199, 276-299
	X	C013	BJ	W0188	11G	22		32-45-11	275-299
	X	C013	BJ	W0192	22R	22		32-45-11	ALL
	X	C013	BJ	W0198	11A	22		32-45-11	050-099, 150-199
	D	C014	2	W0188	109	24		78-36-11	ALL
	D	C014	2	W0188	110	22		78-36-11	ALL
	D	C015	2	W0192	06T	22		78-36-21	ALL
	D	C015	2	W0192	85K	22		78-36-21	ALL
	D	C016	2	W0198	558	22		26-16-21	ALL
	D	C017	2	W0198	559	22		26-16-21	ALL
	D	C018	2	W0192	837	22		29-11-12	ALL
	D	C019	2	W0198	088	24		28-25-11	ALL
	D	C020	2	W0192	836	24		29-11-12	ALL
	D	C021	2	W0192	70P	20		76-11-11	ALL
	D	C021	2	W0198	525	24		76-11-11	ALL
	D	C022	2	W0192	123	22		49-61-11	ALL
	D	C022	2	W0198	009	22		49-61-11	ALL
	D	C023	2	W0192	811	22		36-11-52	ALL
	D	C024	2	W0198	535R	22		26-15-12	ALL
	D	C025	2	W0192	10N	22		29-11-12	ALL
	D	C025	2	W0192	893	22		27-09-13	ALL
	D	C026	2	W0192	10M	24		29-11-12	ALL
	D	C026	2	W0192	892	22		27-09-13	ALL
	Y	C029	BJ	W0188	70A	24		21-61-51	ALL
	Y	C029	BJ	W0192	13B	24		21-61-81	ALL
	Y	C029	BJ	W0192	72H	24		21-61-81	ALL
	Y	C029	BJ	W0192	72J	24		21-61-81	ALL
	D	C031	2	W0188	135	24		36-11-41	ALL
	D	C031	2	W0192	13I	24		36-11-41	ALL
	Y	C033	BJ	W0192	13K	24		36-11-41	ALL
	Y	C033	BJ	W0192	13L	24		36-11-41	ALL
	Y	C033	BJ	W0192	13M	24		36-11-41	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 83

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0274		<b>BACT44B0910U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0274	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	D	C035	2	W0198	136	20		76-11-11	ALL
	D	C036	2	W0192	06G	22		73-21-19	275-299
	D	C036	2	W0192	79U	22		73-21-19	275-299
	D	C037	2	W0192	79U	22		73-21-19	275-299
	D	C038	2	W0198	041	24		29-21-31	ALL
	D	C038	2	W0198	179	24		29-21-31	ALL
	Y	C039	BJ	W0192	238B	24		32-42-11	ALL
	Y	C039	BJ	W0192	248B	24		27-32-21	ALL
	Y	C039	BJ	W0192	292B	24		32-42-11	ALL
	Y	C039	BJ	W0192	901B	24		34-53-21	275-299
	D	C041	2	W0188	70C	20		29-11-14	ALL
	Y	CAP	Y	W0192	51B	24		78-36-21	050-099, 151, 162-166, 275-276
	Y	CAP	Y	W0192	51B	24		SPARE	167-199, 277-299
	Y	CAP	Y	W0192	51C	24		78-36-21	050-099, 150-156, 162-166, 275-276
	Y	CAP	Y	W0192	51C	24		SPARE	157, 167-199, 277-299
	Y	CAP	Y	W0192	51F	24		78-36-21	050-099, 150-156, 162-166, 275-276
	Y	CAP	Y	W0192	51F	24		SPARE	157, 167-199, 277-299
	D	CAP	Y	W0192	66A	24		SPARE	050-099, 155-156, 162-166
	X	D012	BJ	W0192	852	22		78-36-21	ALL
	X	D012	BJ	W0192	857	22		78-36-21	ALL
	X	D013	BJ	W0192	59W	24		24-27-41	050-099, 162-199, 275-299
	X	D013	BJ	W0198	50C	24		24-27-41	050-099, 162-199, 275-299
	D	DED		W0188	126Z			29-11-12	ALL
	X	DED		W0192	04GZ			21-58-14	150-154, 275
	Y	DED		W0192	78BZ			78-34-21	ALL
	X	DED		W0192	857Z			78-36-21	ALL
	Y	DED		W0198	634Z			78-34-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 84

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0276		<b>BACT44B1870U</b>					<b>P054-00/ /</b>		<b>ALL</b>
TB0276	Y	<b>BACM15C3B</b>					<b>P054-00/ /</b>		<b>ALL</b>
TB0276	Z	<b>BACM15C3C</b>					<b>P054-00/ /</b>		<b>ALL</b>
	Z	1	BJ	W1082	081R	22		26-11-11	ALL
	Z	1	BJ	W1082	122R	22		26-11-11	ALL
	Z	1	BJ	W1082	574R	24		26-16-11	ALL
	Z	1	BJ	W1082	575R	24		26-16-11	ALL
	Z	1	BJ	W1082	581R	22		26-11-21	ALL
	Z	1	BJ	W1082	649R	22		26-17-11	ALL
	Z	1	BJ	W1082	691R	22		26-15-11	ALL
	Z	14	BJ	W1082	120R	22		49-61-11	ALL
	Z	14	BJ	W1082	502	24		31-51-21	ALL
	Z	14	BJ	W1082	620R	22		26-15-12	ALL
	Z	14	BJ	W1082	624R	22		26-15-11	ALL
	Z	14	BJ	W1082	692R	22		26-15-11	ALL
	Z	14	BJ	W1082	729R	22		26-15-11	ALL
	Z	15	BJ	W1082	071R	24		26-16-11	ALL
	Z	15	BJ	W1082	073R	24		26-16-11	ALL
	Z	15	BJ	W1082	131R	24		26-16-11	ALL
	Z	15	BJ	W1082	133R	24		26-16-11	ALL
	Z	15	BJ	W1082	134R	24		26-16-11	ALL
	Z	16	BJ	W1082	571R	24		26-16-11	ALL
	Z	16	BJ	W1082	573R	24		26-16-11	ALL
	Z	16	BJ	W1082	631R	24		26-16-11	ALL
	Z	16	BJ	W1082	633R	24		26-16-11	ALL
	Z	16	BJ	W1082	634R	24		26-16-11	ALL
	Z	2	BJ	W1082	069R	24		26-16-11	ALL
	Z	2	BJ	W1082	089R	22		26-11-11	ALL
	Z	2	BJ	W1082	123R	22		26-11-11	ALL
	Z	2	BJ	W1082	589R	22		26-11-21	ALL
	Z	2	BJ	W1082	699R	22		26-15-11	ALL
	Z	2	BJ	W1082	710R	22		26-11-11	ALL
	Y	A005	BJ	W1082	001R	22		26-11-11	ALL
	Y	A005	BJ	W1082	051R	22		26-11-11	ALL
	Y	A005	BJ	W1082	052R	22		26-11-11	ALL
	Y	A006	BJ	W1082	011R	22		26-11-12	ALL
	Y	A006	BJ	W1082	061R	22		26-11-12	ALL
	Y	A006	BJ	W1082	062R	22		26-11-12	ALL
	Y	A007	BJ	W1082	082R	22		26-11-11	ALL
	Y	A007	BJ	W1082	104R	22		26-11-11	ALL
	Y	A007	BJ	W1082	707R	22		26-11-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 85

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0276		<b>BACT44B1870U (continued)</b>					<b>P054-00/ /</b>		<b>ALL</b>
TB0276	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P054-00/ /</b>		<b>ALL</b>
TB0276	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P054-00/ /</b>		<b>ALL</b>
	Y	A007	BJ	W1082	812	24		31-51-21	ALL
	Y	A008	BJ	W1082	501R	22		26-11-21	ALL
	Y	A008	BJ	W1082	551R	22		26-11-21	ALL
	Y	A008	BJ	W1082	552R	22		26-11-21	ALL
	Y	A009	BJ	W1082	511R	22		26-11-22	ALL
	Y	A009	BJ	W1082	561R	22		26-11-22	ALL
	Y	A009	BJ	W1082	562R	22		26-11-22	ALL
	Y	A010	BJ	W1082	002	24		31-51-21	ALL
	Y	A010	BJ	W1082	582R	22		26-11-21	ALL
	Y	A010	BJ	W1082	604R	22		26-11-21	ALL
	Y	A010	BJ	W1082	727R	22		26-11-21	ALL
	Y	A017	BJ	W1082	072R	22		26-16-11	ALL
	Y	A017	BJ	W1082	139R	22		26-16-11	ALL
	Y	A017	BJ	W1082	712R	24		26-16-11	ALL
	Y	A017	BJ	W1082	811	24		31-51-21	ALL
	Y	A019	BJ	W1082	074R	24		26-16-11	ALL
	Y	A019	BJ	W1082	075R	24		26-16-11	ALL
	Y	A019	BJ	W1082	143R	24		26-16-11	ALL
	Y	A020	BJ	W1082	503	24		31-51-21	ALL
	Y	A020	BJ	W1082	735R	22		26-17-11	ALL
	Y	A020	BJ	W1082	842R	22		26-17-11	ALL
	Y	C005	BJ	W1082	101R	22		26-11-11	ALL
	Y	C005	BJ	W1082	151R	22		26-11-11	ALL
	Y	C005	BJ	W1082	152R	22		26-11-11	ALL
	Y	C006	BJ	W1082	111R	22		26-11-12	ALL
	Y	C006	BJ	W1082	161R	22		26-11-12	ALL
	Y	C006	BJ	W1082	162R	22		26-11-12	ALL
	Y	C007	BJ	W1082	121R	22		26-15-11	ALL
	Y	C007	BJ	W1082	171R	22		26-15-11	ALL
	Y	C007	BJ	W1082	172R	22		26-15-11	ALL
	Y	C008	BJ	W1082	601R	22		26-11-21	ALL
	Y	C008	BJ	W1082	651R	22		26-11-21	ALL
	Y	C008	BJ	W1082	652R	22		26-11-21	ALL
	Y	C009	BJ	W1082	611R	22		26-11-22	ALL
	Y	C009	BJ	W1082	661R	22		26-11-22	ALL
	Y	C009	BJ	W1082	662R	22		26-11-22	ALL
	Y	C010	BJ	W1082	621R	22		26-15-11	ALL
	Y	C010	BJ	W1082	671R	22		26-15-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 86

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0276</b>		<b>BACT44B1870U (continued)</b>					<b>P054-00/ /</b>		<b>ALL</b>
<b>TB0276</b>	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P054-00/ /</b>		<b>ALL</b>
<b>TB0276</b>	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P054-00/ /</b>		<b>ALL</b>
	Y	C010	BJ	W1082	672R	22		26-15-11	ALL
	Y	C017	BJ	W1082	003	24		31-51-21	ALL
	Y	C017	BJ	W1082	572R	22		26-16-11	ALL
	Y	C017	BJ	W1082	639R	22		26-16-11	ALL
	Y	C017	BJ	W1082	732R	24		26-16-11	ALL
<b>TB0278</b>		<b>BACT44B0200U</b>					<b>0194/295/L029</b>		<b>ALL</b>
<b>TB0278</b>	<b>R</b>	<b>RESISTORBLOCK-REF233T4403-</b>					<b>0194/295/L029</b>		<b>ALL</b>
	R	A001	2	W0062	12W	24		33-13-16	ALL
	R	A001	2	W0062	234R	24		33-13-16	ALL
	R	A002	2	W0062	12Z	24		33-13-16	ALL
	R	C001	2	W0062	234B	24		33-13-16	ALL
	R	C002	2	W0062	12W	24		33-13-16	ALL
<b>TB0286</b>		<b>BACT44A0460D</b>					<b>P011-05/ /</b>		<b>ALL</b>
<b>TB0286</b>	<b>D</b>	<b>DIODEBLOCK-REF233T5216-</b>					<b>P011/05/</b>		<b>ALL</b>
	D	A001	2	W0044	004R	22		26-11-11	ALL
	D	A002	2	W0042	730R	22		26-11-11	ALL
	D	A003	2	W0042	732R	22		26-11-12	ALL
	D	A004	2	W0044	006R	22		26-11-12	ALL
	D	A005	2	W0044	029R	22		26-11-21	ALL
	D	A006	2	W0042	734R	22		26-11-21	ALL
	D	A007	2	W0044	031R	22		26-11-22	ALL
	D	A008	2	W0042	736R	22		26-11-22	ALL
	D	A009	2	W0044	013R	22		26-15-11	ALL
	D	A010	2	W0042	738R	22		26-15-11	ALL
	D	A011	2	W0044	007R	24		26-16-11	ALL
	D	A012	2	W0042	740R	24		26-16-11	ALL
	D	C001	2	W0042	731R	22		26-11-11	ALL
	D	C001	2	W0044	745R	22		26-11-11	ALL
	D	C002	2	W0042	731R	22		26-11-11	ALL
	D	C003	2	W0042	733R	22		26-11-12	ALL
	D	C004	2	W0042	733R	22		26-11-12	ALL
	D	C004	2	W0044	746R	22		26-11-12	ALL
	D	C005	2	W0042	735R	22		26-11-21	ALL
	D	C005	2	W0044	747R	22		26-11-21	ALL
	D	C006	2	W0042	735R	22		26-11-21	ALL
	D	C007	2	W0042	737R	22		26-11-22	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 87

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0286</b>		<b>BACT44A0460D (continued)</b>					<b>P011-05/ /</b>		<b>ALL</b>
<b>TB0286</b>	<b>D</b>	<b>DIODEBLOCK-REF233T5216- (continued)</b>					<b>P011/05/</b>		<b>ALL</b>
	D	C007	2	W0044	748R	22		26-11-22	ALL
	D	C008	2	W0042	737R	22		26-11-22	ALL
	D	C009	2	W0042	739R	22		26-15-11	ALL
	D	C009	2	W0044	749R	22		26-15-11	ALL
	D	C010	2	W0042	739R	22		26-15-11	ALL
	D	C011	2	W0042	741R	24		26-16-11	ALL
	D	C011	2	W0044	750R	24		26-16-11	ALL
	D	C012	2	W0042	741R	24		26-16-11	ALL
<b>TB0288</b>		<b>284T0384</b>					<b>SHELF/E01/02</b>		<b>ALL</b>
<b>TB0288</b>	<b>D</b>	<b>DIODEBLOCK-REF284T0112-</b>					<b>SHELF/E01/02</b>		<b>ALL</b>
	D	A001	2	W1092	068	24		32-61-14	ALL
	D	A002	2	W1092	534	24		32-61-14	ALL
	D	A003	2	W1092	556	24		32-61-14	ALL
	D	A004	2	W1092	705	24		32-61-14	ALL
	D	A005	2	W1092	142	24		31-51-42	ALL
	D	A005	2	W1092	719	24		32-61-14	ALL
	D	A006	2	W1092	720	24		32-61-14	ALL
	D	C001	2	W1092	039	24		32-61-14	ALL
	D	C001	2	W1100	112	24		32-61-14	ALL
	D	C002	2	W1092	041	24		32-61-14	ALL
	D	C002	2	W1100	115	24		32-61-14	ALL
	D	C003	2	W1092	043	24		32-61-14	ALL
	D	C003	2	W1100	117	24		32-61-14	ALL
	D	C004	2	W1092	042	24		32-61-14	ALL
	D	C004	2	W1100	116	24		32-61-14	ALL
	D	C005	2	W1092	718	24		32-61-14	ALL
	D	C006	2	W1092	721	24		32-61-14	ALL
	D	DED		W1092	039Z			32-61-14	ALL
	D	DED		W1092	041Z			32-61-14	ALL
	D	DED		W1092	042Z			32-61-14	ALL
	D	DED		W1092	043Z			32-61-14	ALL
	D	DED		W1092	721Z			32-61-14	ALL
<b>TB0292</b>		<b>BACT44B0300U</b>					<b>0200/276/R010</b>		<b>ALL</b>
<b>TB0292</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P011-00/ /</b>		<b>ALL</b>
	F	A001	2	W0040	193	24		24-51-31	ALL
	F	A001	2	W0040	197	24		24-51-31	ALL
	F	A002	2	W0042	168	24		24-51-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0200

Page 88

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0292		<b>BACT44B0300U (continued)</b>					<b>0200/276/R010</b>		<b>ALL</b>
TB0292	F	<b>BACM15C1A (continued)</b>					<b>P011-00/ /</b>		<b>ALL</b>
	F	A002	2	W0042	181	24		24-51-31	ALL
	F	A003	2	W0044	196	24		24-51-31	ALL
	F	A003	2	W0044	197	24		24-51-31	ALL
	F	A004	2	W0042	191	22		23-51-21	ALL
	F	A004	2	W0042	196	22		23-51-21	ALL
	F	A005	2	W0042	192	22		23-51-11	ALL
	F	A005	2	W0042	193	22		23-51-11	ALL
	F	A006	2	W0044	192	22		23-51-21	ALL
	F	A006	2	W0044	727	22		23-51-21	ALL
	F	A007	2	W0044	193	22		23-51-11	ALL
	F	A007	2	W0044	725	22		23-51-11	ALL
	F	C002	2	W0036	132	20		24-51-43	ALL
	F	C002	2	W0280	014	20		24-51-43	ALL
	F	C003	2	W0036	133	20		24-51-43	ALL
	F	C003	2	W0280	015	20		24-51-43	ALL
	F	C004	2	W0036	134	20		24-51-43	ALL
	F	C004	2	W0280	016	20		24-51-43	ALL
	F	C005	2	W0038	125	20		24-51-43	ALL
	F	C005	2	W0280	011	20		24-51-43	ALL
	F	C006	2	W0038	121	20		24-51-43	ALL
	F	C006	2	W0280	012	20		24-51-43	ALL
TB0294		<b>BACT44B0220U</b>					<b>P049-00/ /</b>		<b>ALL</b>
TB0294	F	<b>BACM15C1A</b>					<b>P049-00/ /</b>		<b>ALL</b>
TB0294	G	<b>BACM15C1B</b>					<b>P049-00/ /</b>		<b>ALL</b>
TB0294	R	<b>RESISTORBLOCK-REF284T0398-</b>					<b>P049-00/ /</b>		<b>275-276</b>
	G	3	2	W0030	133	20		38-32-14	ALL
	G	3	2	W0030	136	18		38-32-14	050-099, 150-199, 277-299
	G	3	2	W0030	138	18		38-32-14	050-099, 150-199, 277-299
	G	3	2	W0030	144	22		38-32-14	275-276
	G	3	2	W0030	154	22		38-32-14	275-276
	F	A001	2	W1050	036	16		49-61-11	ALL
	F	A001	2	W1050	081	16		49-61-11	ALL
	F	A002	2	W1050	045	16		49-61-11	ALL
	F	A002	2	W1050	082	16		49-61-11	ALL
	R	A004	2	W0030	141	22		38-32-14	275-276
	R	A005	2	W0030	143	22		38-32-14	275-276
	R	C004	2	W0030	142	22		38-32-14	275-276
	R	C005	2	W0030	144	22		38-32-14	275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0200

Page 89

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0300	D	DIODEBLOCK-REF284T1149-					P049-00/ /		050-099
TB0300	F	BACM15C1A					P049-00/ /		ALL
TB0300	G	BACM15C1B					P049-00/ /		ALL
TB0300	X	BACM15C3A					P049-00/ /		ALL
TB0300	Y	BACM15C3B					P049-00/ /		ALL
TB0300	Z	BACM15C3C					P049-00/ /		ALL
	G	10	2	W1050	019	16		49-15-11	ALL
	G	10	2	W1050	064	24		31-31-22	ALL
	G	10	2	W1050	119	16		49-15-11	ALL
	Z	19	BJ	W1050	028	22		49-61-11	ALL
	Z	19	BJ	W1050	031	22		49-41-11	ALL
	Z	19	BJ	W1050	032	22		49-41-11	ALL
	Z	19	BJ	W1050	035	22		49-61-11	ALL
	Z	19	BJ	W1050	039	22		49-61-11	ALL
	G	21	2	W1050	037	16		49-61-11	ALL
	G	21	2	W1050	038	16		49-61-11	ALL
	G	21	2	W1050	041	16		49-61-11	ALL
	G	21	2	W1050	042	16		49-61-11	ALL
	G	22	2	W1050	023	16		49-15-11	ALL
	G	22	2	W1050	043	16		49-15-11	ALL
	G	22	2	W1050	050	22		49-15-11	ALL
	Z	4	BJ	W0030	034	24		36-11-41	ALL
	Z	4	BJ	W0030	037	24		36-11-41	ALL
	Z	4	BJ	W0030	040	24		36-11-41	ALL
	Z	4	BJ	W0030	041	24		36-11-41	ALL
	Z	4	BJ	W0030	042	24		36-11-41	ALL
	Z	4	BJ	W0030	131	24		36-11-41	ALL
	G	7	2	W0030	009	22		38-32-11	ALL
	G	7	2	W0030	017	18		38-32-11	ALL
	G	7	2	W0030	018	18		38-32-11	050-099, 150-155, 162-165, 275-276
	G	7	2	W0030	018	18		38-32-15	156-157, 166-199, 277-299
	G	7	2	W0030	148	22		38-32-15	156-157, 166-199, 277-299
	G	7	2	W0030	154	22		38-32-14	275-276
	Y	A002	BJ	W0030	019	24		21-44-11	ALL
	Y	A002	BJ	W0030	031	24		21-44-11	ALL
	Y	A002	BJ	W0030	033	24		21-44-11	ALL
	Y	A005	BJ	W0030	003	24		38-15-11	ALL
	Y	A005	BJ	W0030	004	24		38-15-11	ALL
	Y	A005	BJ	W1050	098	24		38-15-11	ALL
	F	A014	2	W0030	129	24		31-31-22	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0300

Page 1 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity	
TB0300	D	<b>DIODEBLOCK-REF284T1149- (continued)</b>						<b>P049-00/ /</b>		<b>050-099</b>
TB0300	F	<b>BACM15C1A (continued)</b>						<b>P049-00/ /</b>		<b>ALL</b>
TB0300	G	<b>BACM15C1B (continued)</b>						<b>P049-00/ /</b>		<b>ALL</b>
TB0300	X	<b>BACM15C3A (continued)</b>						<b>P049-00/ /</b>		<b>ALL</b>
TB0300	Y	<b>BACM15C3B (continued)</b>						<b>P049-00/ /</b>		<b>ALL</b>
TB0300	Z	<b>BACM15C3C (continued)</b>						<b>P049-00/ /</b>		<b>ALL</b>
	F	A014	2	W1050	129	24		31-31-22	ALL	
	Y	A015	BJ	W1050	013	20		24-32-41	275-299	
	Y	A015	BJ	W1050	025	20		24-32-41	275-299	
	Y	A015	BJ	W1050	073	20		24-32-41	275-299	
	Y	A016	BJ	W1050	065	20		24-32-41	275-299	
	Y	A016	BJ	W1050	067	20		24-32-41	275-299	
	Y	A016	BJ	W1050	068	20		24-32-41	275-299	
	Y	A017	BJ	W1050	022	24		49-15-11	ALL	
	Y	A017	BJ	W1050	051	24		49-15-11	ALL	
	Y	A017	BJ	W1050	052	24		49-15-11	ALL	
	X	B011	BJ	W0030	083	24		24-51-71	ALL	
	X	B011	BJ	W1050	092	24		24-51-71	ALL	
	Y	C002	BJ	W0030	013	24		21-44-11	ALL	
	Y	C002	BJ	W0030	091	24		21-44-11	ALL	
	Y	C002	BJ	W0030	092	24		21-44-11	ALL	
	Y	C005	BJ	W0030	020	24		38-15-11	ALL	
	Y	C005	BJ	W0030	025	22		38-15-11	ALL	
	Y	C005	BJ	W0030	056	24		38-15-11	ALL	
	Y	C009	BJ	W0030	062	24		24-31-41	ALL	
	Y	C009	BJ	W0030	126	22		24-31-41	ALL	
	Y	C009	BJ	W1050	026	24		24-31-41	ALL	
	X	C011	BJ	W0030	084	24		24-51-71	ALL	
	X	C011	BJ	W1050	093	24		24-51-71	ALL	
	F	C014	2	W0030	130	24		31-31-22	ALL	
	F	C014	2	W1050	130	24		31-31-22	ALL	
	Y	C015	BJ	W1050	055	20		24-32-41	275-299	
	Y	C015	BJ	W1050	056	20		24-32-41	275-299	
	Y	C016	BJ	W1050	024	22		49-41-11	275-299	
	Y	C016	BJ	W1050	057	20		24-32-41	275-299	
	Y	C016	BJ	W1050	105	22		49-41-11	275-299	
	Y	C017	BJ	W1050	009	20		24-32-41	275-299	
	Y	C017	BJ	W1050	101	20		24-32-41	275-299	
	Y	C017	BJ	W1050	102	20		24-32-41	275-299	

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 2

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0302		BACT44B1200U					P036-00/ /		ALL
TB0302	D	DIODEBLOCK-REF284T0187-					P036-00/ /		050-099, 155-199, 276-299
TB0302	F	BACM15C1A					P036-00/ /		ALL
TB0302	G	BACM15C1B					P036-00/ /		ALL
TB0302	H	BACM15C2A					P036-00/ /		280-299
TB0302	R	RESISTORBLOCK					P036-00/ /		ALL
TB0302	X	BACM15C3A					P036-00/ /		ALL
TB0302	Y	BACM15C3B					P036-00/ /		ALL
TB0302	Z	BACM15C3C					P036-00/ /		ALL
	G	19	2	W0182	041	18		38-32-12	050-099, 150-155, 162-165, 275-276
	G	19	2	W0182	127	18		38-32-12	050-099, 150-155, 162-165, 275-276
	G	19	2	W0182	127	18		38-32-11	156-157, 166-199, 277-299
	G	19	2	W0182	128	18		38-32-12	050-099, 150-155, 162-165, 275-276
	G	19	2	W0182	129	20		38-32-11	156, 166
	G	19	2	W0182	129	22		38-32-11	157, 167-199, 277-299
	G	19	2	W0184	70E	18		38-32-11	156-157, 166-199, 277-299
	Z	21	BJ	W0176	216B	24		73-21-14	ALL
	Z	21	BJ	W0176	241B	24		73-21-14	ALL
	Z	21	BJ	W0176	242B	24		73-21-14	ALL
	Z	21	BJ	W0176	256B	24		73-21-14	ALL
	Z	22	BJ	W0176	216R	24		73-21-14	ALL
	Z	22	BJ	W0176	241R	24		73-21-14	ALL
	Z	22	BJ	W0176	242R	24		73-21-14	ALL
	Z	22	BJ	W0176	256R	24		73-21-14	ALL
	G	32	2	W0182	153	18		38-32-14	050-099, 150-199
	G	32	2	W0182	154	18		38-32-14	050-099, 150-199
	G	32	2	W0182	155	20		38-32-14	050-099, 150-199
	G	32	2	W0182	168	18		38-32-11	275-276
	G	32	2	W0182	169	18		38-32-11	275-276
	G	32	2	W0184	70E	18		38-32-11	275-276
	X	A001	BJ	W0176	91C	24		73-21-14	ALL
	X	A001	BJ	W0184	91C	24		73-21-14	ALL
	X	A002	BJ	W0176	01F	24		21-44-11	ALL
	X	A002	BJ	W0182	045	22		21-44-11	ALL
	X	A003	BJ	W0176	01G	24		21-44-21	ALL
	X	A003	BJ	W0182	108	22		21-44-21	ALL
	X	A004	BJ	W0176	401B	24		27-51-41	ALL
	X	A004	BJ	W0184	401B	24		27-51-41	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 3

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0302		<b>BACT44B1200U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 155-199, 276-299</b>
TB0302	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>280-299</b>
TB0302	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	X	A005	BJ	W0176	212R	22		27-51-41	ALL
	X	A005	BJ	W0184	203R	22		27-51-41	ALL
	X	A006	BJ	W0176	04U	22		32-41-11	ALL
	X	A006	BJ	W0184	724	22		32-41-11	ALL
	X	A008	BJ	W0176	128	24		24-25-13	ALL
	X	A008	BJ	W0184	866	24		24-25-13	ALL
	F	A009	2	W0176	771	24		21-25-11	ALL
	F	A009	2	W0182	039	18		21-25-11	ALL
	F	A010	2	W0176	107	16		33-45-11	ALL
	F	A010	2	W0180	014	16		33-45-11	ALL
	Y	A011	BJ	W0176	62R	24		21-43-11	275-299
	Y	A011	BJ	W0180	132	24		21-43-11	ALL
	Y	A011	BJ	W0182	510	24		21-43-11	ALL
	Y	A012	BJ	W0176	768	22		28-42-11	ALL
	Y	A012	BJ	W0176	883	24		28-42-11	ALL
	Y	A012	BJ	W0176	884	22		28-42-11	ALL
	Y	A013	BJ	W0176	03W	22		27-23-11	ALL
	Y	A013	BJ	W0176	03X	22		27-23-11	ALL
	Y	A013	BJ	W0176	604	22		27-23-11	ALL
	Y	A014	BJ	W0176	573	24		27-28-13	ALL
	Y	A014	BJ	W0176	574	24		27-28-13	ALL
	Y	A014	BJ	W0176	577	24		27-28-13	ALL
	Y	A015	BJ	W0184	503	22		32-41-11	ALL
	Y	A015	BJ	W0184	507	22		32-41-11	ALL
	Y	A015	BJ	W0184	508	22		32-41-11	ALL
	Y	A015	BJ	W0184	781	24		32-41-11	ALL
	Y	A016	BJ	W0176	235B	24		73-21-14	ALL
	Y	A016	BJ	W0176	237B	24		73-21-14	ALL
	Y	A016	BJ	W0176	238B	24		73-21-14	ALL
	Y	A016	BJ	W0184	208B	24		73-21-14	ALL
	Y	A017	BJ	W0176	216Z			73-21-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 4

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0302		<b>BACT44B1200U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 155-199, 276-299</b>
TB0302	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>280-299</b>
TB0302	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	A017	BJ	W0176	241Z			73-21-14	050-099, 275-299
	Y	A017	BJ	W0176	242Z			73-21-14	ALL
	Y	A017	BJ	W0176	256Z			73-21-14	ALL
	Y	A018	BJ	W0176	235Z			73-21-14	ALL
	Y	A018	BJ	W0176	237Z			73-21-14	ALL
	Y	A018	BJ	W0176	238Z			73-21-14	ALL
	Y	A018	BJ	W0184	208Z			73-21-14	ALL
	Y	A024	BJ	W0176	15C	24		21-58-11	050-099, 150-155, 162-165, 275-276
	Y	A024	BJ	W0176	836	24		21-58-11	050-099, 150-155, 162-165, 275-276
	Y	A024	BJ	W0184	849	24		21-58-11	050-099, 150-155, 162-165, 275-276
	Y	A025	BJ	W0176	11X	24		21-61-71	150-199
	Y	A025	BJ	W0176	12X	24		21-61-71	150-199
	Y	A025	BJ	W0176	12Y	24		21-61-71	150-199
	Y	A025	BJ	W0176	13W	24		21-61-71	150-199
	Y	A025	BJ	W0176	18L	20		73-21-11	050-099, 277-299
	Y	A025	BJ	W0176	18R	20		73-21-11	050-099, 277-299
	Y	A025	BJ	W0176	18S	20		73-21-11	050-099, 277-299
	Y	A025	BJ	W0176	18U	20		73-21-11	050-099, 277-299
	Y	A026	BJ	W0176	249R	24		77-31-11	150-157, 275-276
	Y	A026	BJ	W0176	270R	24		77-12-12	150-157, 275-276
	Y	A026	BJ	W0176	271R	24		77-12-12	150-157, 275-276
	Y	A027	BJ	W0176	249Z			77-31-11	150-157, 275-276
	Y	A027	BJ	W0176	270Z			77-12-12	150-157, 275-276
	Y	A027	BJ	W0176	271Z			77-12-12	150-157, 275-276
	Y	A028	BJ	W0176	35A	20		21-66-11	050-099, 162-199
	Y	A028	BJ	W0176	46A	22		21-66-11	050-099, 162-199
	Y	A028	BJ	W0176	47A	22		21-66-11	050-099, 162-199
	Y	A029	BJ	W0176	209B	24		36-21-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 5

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0302		<b>BACT44B1200U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 155-199, 276-299</b>
TB0302	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>280-299</b>
TB0302	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Y	A029	BJ	W0176	259B	24		36-21-11	ALL
	Y	A029	BJ	W0176	260B	24		36-21-11	ALL
	R	A033	2	W0176	341	24		24-11-11	050, 150-199
	R	A033	2	W0176	57C	24		24-11-11	050, 150-199
	Y	A036	BJ	W0176	15C	24		21-58-11	156-157, 166-199, 277-299
	Y	A036	BJ	W0176	836	24		21-58-11	156-157, 166-199, 277-299
	Y	A036	BJ	W0184	849	24		21-58-11	156-157, 166-199, 277-299
	D	A037	2	W0176	76Q	20		28-31-12	050-099, 155-199, 277-299
	D	A037	2	W0184	10B	22		28-31-12	050-099, 155-199, 276-299
	X	B001	BJ	W0176	706	24		21-26-11	ALL
	X	B001	BJ	W0182	070	24		21-26-11	ALL
	X	B002	BJ	W0176	91CZ			73-21-14	ALL
	X	B002	BJ	W0184	91CZ			73-21-14	ALL
	X	B003	BJ	W0176	20B	24		21-43-11	ALL
	X	B003	BJ	W0182	057	24		21-43-11	ALL
	X	B004	BJ	W0176	401R	24		27-51-41	ALL
	X	B004	BJ	W0184	401R	24		27-51-41	ALL
	X	B005	BJ	W0176	212B	22		27-51-41	ALL
	X	B005	BJ	W0184	203B	22		27-51-41	ALL
	X	B006	BJ	W0176	64A	22		30-34-11	ALL
	X	B006	BJ	W0184	64A	22		30-34-11	ALL
	X	B007	BJ	W0176	126	22		24-25-11	ALL
	X	B007	BJ	W0184	864	22		24-25-11	ALL
	X	B008	BJ	W0176	129	24		24-25-13	ALL
	X	B008	BJ	W0184	867	24		24-25-13	ALL
	X	C001	BJ	W0176	20A	24		21-43-11	ALL
	X	C001	BJ	W0182	058	24		21-43-11	ALL
	X	C002	BJ	W0176	776	24		21-44-21	ALL
	X	C002	BJ	W0180	130	24		21-44-21	ALL
	X	C003	BJ	W0176	20C	24		21-43-11	ALL
	X	C003	BJ	W0180	11A	24		21-43-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 6

Feb 06/2009



Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0302		BACT44B1200U (continued)					P036-00/ /		ALL
TB0302	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		050-099, 155-199, 276-299
TB0302	F	BACM15C1A (continued)					P036-00/ /		ALL
TB0302	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0302	H	BACM15C2A (continued)					P036-00/ /		280-299
TB0302	R	RESISTORBLOCK (continued)					P036-00/ /		ALL
TB0302	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0302	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0302	Z	BACM15C3C (continued)					P036-00/ /		ALL
	X	C004	BJ	W0176	401Y	24		27-51-41	ALL
	X	C004	BJ	W0184	401Y	24		27-51-41	ALL
	X	C005	BJ	W0176	869R	22		26-17-11	ALL
	X	C005	BJ	W0184	816R	22		26-17-11	ALL
	X	C007	BJ	W0176	05P	24		32-42-11	ALL
	X	C007	BJ	W0184	830	24		32-42-11	ALL
	X	C008	BJ	W0176	130	24		24-25-13	ALL
	X	C008	BJ	W0184	868	24		24-25-13	ALL
	F	C009	2	W0180	034	18		33-31-21	ALL
	F	C009	2	W0182	098	18		33-31-21	ALL
	F	C010	2	W0176	108	16		33-45-11	ALL
	F	C010	2	W0180	015	16		33-45-11	ALL
	Y	C012	BJ	W0176	03U	22		27-13-11	ALL
	Y	C012	BJ	W0176	03V	22		27-13-11	ALL
	Y	C012	BJ	W0176	601	22		27-13-11	ALL
	Y	C013	BJ	W0176	03Y	22		27-23-11	ALL
	Y	C013	BJ	W0176	653	22		27-23-11	ALL
	Y	C013	BJ	W0184	814	22		27-23-11	ALL
	Y	C014	BJ	W0176	03K	22		29-32-11	ALL
	Y	C014	BJ	W0176	03L	24		29-32-11	ALL
	Y	C014	BJ	W0176	616	22		29-32-11	ALL
	Y	C015	BJ	W0176	885	22		79-33-11	ALL
	Y	C015	BJ	W0176	886	22		79-33-11	ALL
	Y	C015	BJ	W0176	887	24		79-33-11	ALL
	Y	C016	BJ	W0176	235R	24		73-21-14	ALL
	Y	C016	BJ	W0176	237R	24		73-21-14	ALL
	Y	C016	BJ	W0176	238R	24		73-21-14	ALL
	Y	C016	BJ	W0184	208R	24		73-21-14	ALL
	Y	C017	BJ	W0176	82S	20		78-34-11	ALL
	Y	C017	BJ	W0176	83B	20		78-34-11	ALL
	Y	C017	BJ	W0184	02H	20		78-34-11	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0300

Page 7

Feb 06/2009



## 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0302		BACT44B1200U (continued)					P036-00/ /		ALL
TB0302	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		050-099, 155-199, 276-299
TB0302	F	BACM15C1A (continued)					P036-00/ /		ALL
TB0302	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0302	H	BACM15C2A (continued)					P036-00/ /		280-299
TB0302	R	RESISTORBLOCK (continued)					P036-00/ /		ALL
TB0302	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0302	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0302	Z	BACM15C3C (continued)					P036-00/ /		ALL
	F	C020	2	W0182	128	22		38-32-11	156-157, 166-199, 277-299
	F	C020	2	W0182	70C	22		38-32-11	156-157, 166-199, 277-299
	F	C020	2	W0184	70R	18		38-32-11	156-157, 166-199, 277-299
	Y	C024	BJ	W0176	70K	22		32-45-11	050-099, 150-199
	Y	C024	BJ	W0184	11J	22		32-45-11	050-099, 150-199
	Y	C025	BJ	W0176	15B	24		21-58-11	ALL
	Y	C025	BJ	W0176	15J	24		21-58-11	ALL
	Y	C025	BJ	W0176	15K	24		21-58-11	ALL
	Y	C025	BJ	W0176	241Z			73-21-14	150-199
	Y	C026	BJ	W0176	249B	24		77-31-11	150-157, 275-276
	Y	C026	BJ	W0176	270B	24		77-12-12	150-157, 275-276
	Y	C026	BJ	W0176	271B	24		77-12-12	150-157, 275-276
	Y	C027	BJ	W0056	069	22		21-66-11	050-099, 162-199
	Y	C027	BJ	W0176	29A	22		21-66-11	050-099, 162-199
	Y	C027	BJ	W0176	30A	22		21-66-11	050-099, 162-199
	Y	C027	BJ	W0176	31A	22		21-66-11	050-099, 162-199
	Y	C029	BJ	W0176	209R	24		36-21-11	ALL
	Y	C029	BJ	W0176	259R	24		36-21-11	ALL
	Y	C029	BJ	W0176	260R	24		36-21-11	ALL
	F	C030	2	W0182	137	18		21-24-11	150-199
	F	C030	2	W0184	756	18		21-24-11	150-199
	F	C031	2	W0182	137	18		21-24-11	050-099
	F	C031	2	W0184	756	18		21-24-11	050-099
	R	C033	2	W0176	327	24		24-11-11	050, 150-199
	R	C033	2	W0176	59N	24		24-11-11	050, 150-199
	D	C037	2	W0176	75C	22		28-31-12	050-099, 155-199, 276-299
	D	C037	2	W0176	75E	22		28-31-12	050-099, 155-199, 276-299
	X	D002	BJ	W0176	09A	24		21-44-21	ALL
	X	D002	BJ	W0182	512	24		21-44-21	ALL
	X	D003	BJ	W0176	593	24		27-38-11	ALL
	X	D003	BJ	W0180	126	24		27-38-11	ALL

### TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 8

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0302		<b>BACT44B1200U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	D	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 155-199, 276-299</b>
TB0302	F	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	G	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	H	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>280-299</b>
TB0302	R	<b>RESISTORBLOCK (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	X	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	Y	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0302	Z	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	X	D004	BJ	W0176	401G	24		27-51-41	ALL
	X	D004	BJ	W0184	401G	24		27-51-41	ALL
	X	D005	BJ	W0176	623	24		23-31-13	ALL
	X	D005	BJ	W0180	058	24		23-31-13	ALL
	X	D007	BJ	W0176	127	22		24-25-11	ALL
	X	D007	BJ	W0184	865	22		24-25-11	ALL
	X	D008	BJ	W0176	131	24		24-25-13	ALL
	X	D008	BJ	W0184	869	24		24-25-13	ALL
	Y	DED		W0176	03YZ			27-23-11	ALL
	X	DED		W0176	04UZ			32-41-11	ALL
	Y	DED		W0176	653Z			27-23-11	ALL
	D	DED		W0176	75CZ			28-31-12	050-099, 155-199, 276-299
	D	DED		W0176	75EZ			28-31-12	050-099, 155-199, 276-299
	Y	DED		W0176	768Z			28-42-11	ALL
	D	DED		W0176	76QZ			28-31-12	050-099, 155-199, 277-299
	Y	DED		W0176	83BZ			78-34-11	ALL
	Y	DED		W0176	883Z			28-42-11	ALL
	Y	DED		W0176	884Z			28-42-11	ALL
	Y	DED		W0184	02HZ			78-34-11	ALL
	D	DED		W0184	10BZ			28-31-12	050-099, 155-199, 276-299
TB0304		<b>BACT44B1200U</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	F	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	G	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	H	<b>BACM15C2A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	R	<b>RESISTORBLOCK</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	X	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	Y	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	Z	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	21	BJ	W0192	225B	24		73-21-14	ALL
	Z	21	BJ	W0192	226B	24		73-21-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 9

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0304		<b>BACT44B1200U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	F	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	G	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	H	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	R	<b>RESISTORBLOCK (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	21	BJ	W0192	268B	24		73-21-14	ALL
	Z	21	BJ	W0192	281B	24		73-21-14	ALL
	Z	22	BJ	W0192	225R	24		73-21-14	ALL
	Z	22	BJ	W0192	226R	24		73-21-14	ALL
	Z	22	BJ	W0192	268R	24		73-21-14	ALL
	Z	22	BJ	W0192	281R	24		73-21-14	ALL
	H	29	2	W0192	67L	22		73-21-11	ALL
	H	29	2	W0192	67N	22		73-21-11	ALL
	H	29	2	W0192	67X	20		73-21-11	ALL
	H	29	2	W0192	68A	16		73-21-11	ALL
	H	29	2	W0192	68C	16		73-21-11	ALL
	G	31	2	W0188	121	18		33-44-21	ALL
	G	31	2	W0192	136	18		33-44-21	ALL
	G	31	2	W0192	894	18		33-44-21	ALL
	G	33	2	W0198	042	24		29-21-31	ALL
	G	33	2	W0198	114	24		29-21-31	ALL
	G	33	2	W0198	526	24		29-21-31	ALL
	X	A001	BJ	W0192	154	24		21-25-21	ALL
	X	A001	BJ	W1118	053	24		21-25-21	ALL
	X	A002	BJ	W0192	768	24		21-51-21	ALL
	X	A002	BJ	W1118	129	24		21-51-21	ALL
	X	A003	BJ	W0192	09D	24		21-53-21	ALL
	X	A003	BJ	W1118	172	24		21-53-21	ALL
	X	A004	BJ	W0192	206B	22		21-61-51	ALL
	X	A004	BJ	W0198	201B	22		21-61-51	ALL
	X	A005	BJ	W0188	401G	24		27-51-41	ALL
	X	A005	BJ	W0192	401G	24		27-51-41	ALL
	X	A006	BJ	W0188	201R	22		27-51-41	ALL
	X	A006	BJ	W0192	208R	22		27-51-41	ALL
	X	A007	BJ	W0192	18M	24		73-21-11	ALL
	X	A007	BJ	W0198	183	24		73-21-11	ALL
	X	A008	BJ	W0192	18G	24		73-21-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 10

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0304		BACT44B1200U (continued)					P037-00/ /		ALL
TB0304	F	BACM15C1A (continued)					P037-00/ /		ALL
TB0304	G	BACM15C1B (continued)					P037-00/ /		ALL
TB0304	H	BACM15C2A (continued)					P037-00/ /		ALL
TB0304	R	RESISTORBLOCK (continued)					P037-00/ /		ALL
TB0304	X	BACM15C3A (continued)					P037-00/ /		ALL
TB0304	Y	BACM15C3B (continued)					P037-00/ /		ALL
TB0304	Z	BACM15C3C (continued)					P037-00/ /		ALL
	X	A008	BJ	W0198	182	24		73-21-11	ALL
	X	A009	BJ	W0192	14GZ			73-21-11	275-276
	X	A009	BJ	W0198	028Z			73-21-11	275-276
	X	A010	BJ	W0192	262B	24		21-51-21	ALL
	X	A010	BJ	W1118	203B	24		21-51-21	ALL
	Y	A011	BJ	W0192	03G	24		21-44-11	ALL
	Y	A011	BJ	W1118	050	22		21-44-11	ALL
	Y	A011	BJ	W1118	081	22		21-44-11	ALL
	Y	A012	BJ	W0192	03K	24		21-51-21	ALL
	Y	A012	BJ	W0192	03L	24		21-51-21	ALL
	Y	A012	BJ	W0192	09A	24		21-51-21	ALL
	Y	A013	BJ	W0192	20K	24		21-61-81	ALL
	Y	A013	BJ	W0192	70K	24		21-61-81	ALL
	Y	A013	BJ	W0192	70M	24		21-61-81	ALL
	Y	A014	BJ	W0192	06B	22		28-42-11	ALL
	Y	A014	BJ	W0192	06C	24		28-42-11	ALL
	Y	A014	BJ	W0192	654	22		28-42-11	ALL
	Y	A015	BJ	W0192	08H	22		27-23-11	ALL
	Y	A015	BJ	W0192	08J	22		27-23-11	ALL
	Y	A015	BJ	W0192	542	22		27-23-11	ALL
	Y	A016	BJ	W0192	08D	22		29-33-11	ALL
	Y	A016	BJ	W0192	08E	24		29-33-11	ALL
	Y	A016	BJ	W0192	677	22		29-33-11	ALL
	Y	A017	BJ	W0192	167	24		21-51-21	150-199, 275-299
	Y	A017	BJ	W0192	769	24		21-51-21	150-199, 275-299
	Y	A017	BJ	W1118	130	24		21-51-21	150-199, 275-299
	Y	A018	BJ	W0192	249B	24		73-21-14	ALL
	Y	A018	BJ	W0192	251B	24		73-21-14	ALL
	Y	A018	BJ	W0192	252B	24		73-21-14	ALL
	Y	A018	BJ	W0192	254B	24		73-21-14	ALL
	Y	A019	BJ	W0192	225Z	24		73-21-14	ALL
	Y	A019	BJ	W0192	226Z			73-21-14	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0300

Page 11

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0304		<b>BACT44B1200U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	A019	BJ	W0192	268Z			73-21-14	ALL
	Y	A019	BJ	W0192	281Z			73-21-14	ALL
	Y	A020	BJ	W0192	249Z			73-21-14	ALL
	Y	A020	BJ	W0192	251Z			73-21-14	ALL
	Y	A020	BJ	W0192	252Z			73-21-14	ALL
	Y	A020	BJ	W0192	254Z			73-21-14	ALL
	Y	A023	BJ	W0192	277R	24		77-12-11	ALL
	Y	A023	BJ	W0192	299R	24		77-12-11	ALL
	Y	A024	BJ	W0192	277Z			77-12-11	ALL
	Y	A024	BJ	W0192	299Z			77-12-11	ALL
	Y	A025	BJ	W0192	63B	22		28-42-13	050-099, 155-199, 276-299
	Y	A025	BJ	W0192	63W	22		28-42-13	050-099, 155-199, 276-299
	Y	A025	BJ	W0192	63Y	22		28-42-13	050-099, 155-199, 276-299
	Y	A026	BJ	W0192	67A	22		28-31-11	050-099, 155-199, 276-299
	Y	A026	BJ	W0192	67F	22		28-31-11	050-099, 155-199, 276-299
	Y	A026	BJ	W0192	67G	22		28-31-11	050-099, 155-199, 276-299
	R	A032	2	W0192	346	24		24-11-21	050, 150-199
	R	A032	2	W0192	61C	24		24-11-21	050, 150-199
	Y	A034	BJ	W0192	210R	24		36-21-11	ALL
	Y	A034	BJ	W0192	275R	24		36-21-11	ALL
	Y	A034	BJ	W0192	276R	24		36-21-11	ALL
	D	A037	2	W0188	043	22		28-31-12	276
	D	A037	2	W0192	66X	22		28-31-12	050-099, 155-199, 277-299
	D	A037	2	W0198	516	22		28-31-12	050-099, 155-199, 276-299
	D	A38	2	W0198	564R	22		26-17-11	150, 152-199
	X	B001	BJ	W0192	169	24		21-26-11	ALL
	X	B001	BJ	W1118	137	24		21-26-11	ALL
	X	B002	BJ	W0192	20U	22		21-26-31	275-299
	X	B002	BJ	W0192	769	24		21-51-21	050-099
	X	B002	BJ	W1118	130	24		21-51-21	050-099
	X	B002	BJ	W1118	539	22		21-26-31	275-299
	X	B003	BJ	W0192	09E	24		21-53-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 12

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0304		BACT44B1200U (continued)					P037-00/ /		ALL
TB0304	F	BACM15C1A (continued)					P037-00/ /		ALL
TB0304	G	BACM15C1B (continued)					P037-00/ /		ALL
TB0304	H	BACM15C2A (continued)					P037-00/ /		ALL
TB0304	R	RESISTORBLOCK (continued)					P037-00/ /		ALL
TB0304	X	BACM15C3A (continued)					P037-00/ /		ALL
TB0304	Y	BACM15C3B (continued)					P037-00/ /		ALL
TB0304	Z	BACM15C3C (continued)					P037-00/ /		ALL
	X	B003	BJ	W1118	173	24		21-53-21	ALL
	X	B004	BJ	W0192	206R	22		21-61-51	ALL
	X	B004	BJ	W0198	201R	22		21-61-51	ALL
	X	B005	BJ	W0188	401Y	24		27-51-41	ALL
	X	B005	BJ	W0192	401Y	24		27-51-41	ALL
	X	B006	BJ	W0188	201B	22		27-51-41	ALL
	X	B006	BJ	W0192	208B	22		27-51-41	ALL
	X	B007	BJ	W0192	14G	24		73-21-11	050-099, 150-199, 277-299
	X	B007	BJ	W0198	028	24		73-21-11	050-099, 150-199, 277-299
	X	B008	BJ	W0192	14GZ			73-21-11	050-099, 150-199, 277-299
	X	B008	BJ	W0198	028Z			73-21-11	050-099, 150-199, 277-299
	X	B009	BJ	W0192	095	24		31-31-22	050-099
	X	B009	BJ	W0198	043	24		31-31-22	050-099
	X	B010	BJ	W0192	262R	24		21-51-21	ALL
	X	B010	BJ	W1118	203R	24		21-51-21	ALL
	X	C001	BJ	W0192	766	24		21-51-21	ALL
	X	C001	BJ	W1118	127	24		21-51-21	ALL
	X	C002	BJ	W0192	09B	24		21-53-21	ALL
	X	C002	BJ	W1118	170	24		21-53-21	ALL
	X	C003	BJ	W0192	09F	24		21-53-21	ALL
	X	C003	BJ	W1118	174	24		21-53-21	ALL
	X	C004	BJ	W0192	622	24		36-11-41	ALL
	X	C004	BJ	W0198	519	24		36-11-41	ALL
	X	C005	BJ	W0188	401R	24		27-51-41	ALL
	X	C005	BJ	W0192	401R	24		27-51-41	ALL
	X	C006	BJ	W0188	122	22		29-11-22	ALL
	X	C006	BJ	W0192	01N	22		29-11-22	ALL
	X	C007	BJ	W0192	095	24		31-31-22	150-199, 275-299
	X	C007	BJ	W0198	043	24		31-31-22	150-199, 275-299
	X	C008	BJ	W0192	14G	24		73-21-11	275-276
	X	C008	BJ	W0198	028	24		73-21-11	275-276
	X	C009	BJ	W0192	096	24		31-31-22	050-099

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0300

Page 13

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0304		<b>BACT44B1200U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	C009	BJ	W0198	50D	24		31-31-22	050-099
	X	C010	BJ	W0192	168	24		21-51-21	150-199, 275-299
	X	C010	BJ	W1118	151	24		21-51-21	150-199, 275-299
	Y	C011	BJ	W1118	052	24		21-44-11	ALL
	Y	C011	BJ	W1118	165	24		21-44-11	ALL
	Y	C011	BJ	W1118	166	24		21-44-11	ALL
	Y	C012	BJ	W0192	620	22		36-11-41	ALL
	Y	C012	BJ	W0192	804	22		36-11-41	ALL
	Y	C012	BJ	W0198	548	24		36-11-41	ALL
	Y	C013	BJ	W0188	001	22		28-42-11	ALL
	Y	C013	BJ	W0188	107	22		28-42-11	ALL
	Y	C013	BJ	W0188	108	24		28-42-11	ALL
	Y	C015	BJ	W0192	07Z	22		29-32-11	ALL
	Y	C015	BJ	W0192	08A	24		29-32-11	ALL
	Y	C015	BJ	W0192	772	22		29-32-11	ALL
	Y	C016	BJ	W0192	097	20		33-44-11	ALL
	Y	C016	BJ	W0192	137	20		33-44-11	ALL
	Y	C016	BJ	W0192	816	20		33-44-11	ALL
	Y	C017	BJ	W0192	07K	22		79-33-11	ALL
	Y	C017	BJ	W0192	07L	22		79-33-11	ALL
	Y	C017	BJ	W0192	07M	24		79-33-11	ALL
	Y	C018	BJ	W0192	249R	24		73-21-14	ALL
	Y	C018	BJ	W0192	251R	24		73-21-14	ALL
	Y	C018	BJ	W0192	252R	24		73-21-14	ALL
	Y	C018	BJ	W0192	254R	24		73-21-14	ALL
	Y	C019	BJ	W0192	67M	20		73-21-11	050-099, 277-299
	Y	C019	BJ	W0192	67V	20		73-21-11	050-099, 277-299
	Y	C019	BJ	W0192	67W	20		73-21-11	050-099, 277-299
	Y	C019	BJ	W0192	68D	20		73-21-11	050-099, 277-299
	Y	C019	BJ	W0192	91L	22		76-11-11	150-199
	Y	C019	BJ	W0198	91M	20		76-11-11	150-199
	Y	C019	BJ	W0198	91N	20		76-11-11	150-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 14

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0304		<b>BACT44B1200U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	C020	BJ	W0192	67M	20		73-21-11	150-199, 275-276
	Y	C020	BJ	W0192	67V	20		73-21-11	150-199, 275-276
	Y	C020	BJ	W0192	67W	20		73-21-11	150-199, 275-276
	Y	C020	BJ	W0192	68D	20		73-21-11	150-199, 275-276
	Y	C023	BJ	W0192	277B	24		77-12-11	ALL
	Y	C023	BJ	W0192	299B	24		77-12-11	ALL
	Y	C024	BJ	W0188	11F	24		21-28-11	150
	Y	C024	BJ	W0192	20U	22		21-26-31	050-099, 150-199
	Y	C024	BJ	W1118	539	22		21-26-31	050-099, 150-199
	R	C032	2	W0192	21M	24		24-11-21	050, 150-199
	R	C032	2	W0192	345	24		24-11-21	050, 150-199
	Y	C034	BJ	W0192	210B	24		36-21-11	ALL
	Y	C034	BJ	W0192	275B	24		36-21-11	ALL
	Y	C034	BJ	W0192	276B	24		36-21-11	ALL
	D	C037	2	W0192	66G	22		28-31-12	050-099, 155-199, 276-299
	D	C037	2	W0192	66J	22		28-31-12	050-099, 155-199, 276-299
	D	C38	2	W0198	901	22		26-17-11	150, 152-199
	Y	CAP	Y	W0188	11F	24		21-28-11	151-154
	Y	CAP	Y	W0192	278B	24		77-12-11	ALL
	Y	CAP	Y	W0192	278R	24		77-12-11	050-099
	Y	CAP	Y	W0192	278R	24		77-12-11	150-199, 275-299
	X	D001	BJ	W0192	767	24		21-51-21	ALL
	X	D001	BJ	W1118	128	24		21-51-21	ALL
	X	D002	BJ	W0192	09C	24		21-53-21	ALL
	X	D002	BJ	W1118	171	24		21-53-21	ALL
	X	D003	BJ	W0192	09G	24		21-53-21	ALL
	X	D003	BJ	W1118	175	24		21-53-21	ALL
	X	D004	BJ	W0188	076R	22		26-18-21	ALL
	X	D004	BJ	W0192	531R	22		26-18-21	ALL
	X	D005	BJ	W0188	401B	24		27-51-41	ALL
	X	D005	BJ	W0192	401B	24		27-51-41	ALL
	X	D006	BJ	W0192	512R	22		26-17-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 15

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0304		<b>BACT44B1200U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>R</b>	<b>RESISTORBLOCK (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0304	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	X	D006	BJ	W0198	567R	22		26-17-11	ALL
	X	D007	BJ	W0192	096	24		31-31-22	150-199, 275-299
	X	D007	BJ	W0198	50D	24		31-31-22	150-199, 275-299
	D	DED		W0188	043Z			28-31-12	276
	X	DED		W0188	122Z			29-11-22	ALL
	X	DED		W0192	01NZ			29-11-22	ALL
	Y	DED		W0192	278Z			77-12-11	ALL
	Y	DED		W0192	63BZ			28-42-13	050-099, 155-199, 276-299
	Y	DED		W0192	63WZ			28-42-13	050-099, 155-199, 276-299
	Y	DED		W0192	63YZ			28-42-13	050-099, 155-199, 276-299
	D	DED		W0192	66GZ			28-31-12	050-099, 155-199, 276-299
	D	DED		W0192	66JZ			28-31-12	050-099, 155-199, 276-299
	D	DED		W0192	66XZ			28-31-12	050-099, 155-199, 277-299
	Y	DED		W0192	67AZ			28-31-11	050-099, 155-199, 276-299
	Y	DED		W0192	67FZ			28-31-11	050-099, 155-199, 276-299
	Y	DED		W0192	67GZ			28-31-11	050-099, 155-199, 276-299
	H	DED		W0192	67LZ			73-21-11	ALL
	H	DED		W0192	67NZ			73-21-11	ALL
	D	DED		W0198	516Z			28-31-12	050-099, 155-199, 276-299
	X	DED		W1118	203Z			21-51-21	ALL
<b>TB0306</b>		<b>BACT44B0700U</b>					<b>P035-00/ /</b>		<b>ALL</b>
<b>TB0306</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P035-00/ /</b>		<b>ALL</b>
<b>TB0306</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W1066	39D	22		25-53-16	ALL
	Z	10	BJ	W1066	44E	22		25-53-16	ALL
	Z	10	BJ	W1066	45E	22		25-53-16	ALL
	Z	10	BJ	W1066	46E	22		25-53-16	ALL
	Z	10	BJ	W1066	47E	22		25-53-17	ALL
	Z	10	BJ	W1066	48E	22		25-53-17	ALL
	Z	10	BJ	W1066	49E	22		25-53-17	ALL
	Z	10	BJ	W1066	50E	22		25-53-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 16

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0306		<b>BACT44B0700U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0306	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0306	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	11	BJ	W1066	37V	22		25-53-16	ALL
	Z	11	BJ	W1066	44B	22		25-53-16	ALL
	Z	11	BJ	W1066	45B	22		25-53-16	ALL
	Z	11	BJ	W1066	46B	22		25-53-16	ALL
	Z	11	BJ	W1066	47B	22		25-53-17	ALL
	Z	11	BJ	W1066	48B	22		25-53-17	ALL
	Z	11	BJ	W1066	49B	22		25-53-17	ALL
	Z	11	BJ	W1066	50B	22		25-53-17	ALL
	Z	12	BJ	W1066	195	22		25-53-15	ALL
	Z	12	BJ	W1066	40B	22		25-53-15	ALL
	Z	12	BJ	W1066	41B	22		25-53-15	ALL
	Z	12	BJ	W1066	42B	22		25-53-15	ALL
	Z	12	BJ	W1066	43B	22		25-53-15	ALL
	Z	13	BJ	W1066	03Q	22		25-53-16	ALL
	Z	13	BJ	W1066	03S	22		25-53-16	ALL
	Z	13	BJ	W1066	04C	22		25-53-16	150-199, 275-299
	Z	13	BJ	W1066	37J	22		25-53-16	ALL
	Z	13	BJ	W1066	37L	22		25-53-16	ALL
	Z	13	BJ	W1066	46G	22		25-53-16	ALL
	Z	13	BJ	W1066	50J	22		25-53-16	050-099
	Z	7	BJ	W1066	38D	22		25-53-15	ALL
	Z	7	BJ	W1066	40E	22		25-53-15	ALL
	Z	7	BJ	W1066	41E	22		25-53-15	ALL
	Z	7	BJ	W1066	42E	22		25-53-15	ALL
	Z	7	BJ	W1066	43E	22		25-53-15	ALL
	Z	8	BJ	W1066	01J	22		25-53-13	150-199, 275-299
	Z	8	BJ	W1066	37T	22		25-53-13	ALL
	Z	8	BJ	W1066	37U	22		25-53-13	ALL
	Z	8	BJ	W1066	38E	22		25-53-15	ALL
	Z	8	BJ	W1066	40C	22		25-53-15	ALL
	Z	8	BJ	W1066	41C	22		25-53-15	ALL
	Z	8	BJ	W1066	42C	22		25-53-15	ALL
	Z	8	BJ	W1066	43C	22		25-53-15	ALL
	Z	8	BJ	W1066	50C	22		25-53-17	050-099
	Z	9	BJ	W1066	01D	22		25-53-13	150-199, 275-299
	Z	9	BJ	W1066	03V	22		25-53-16	150-199, 275-299
	Z	9	BJ	W1066	03W	22		25-53-16	150-199, 275-299
	Z	9	BJ	W1066	37U	22		25-53-13	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 17

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0306		<b>BACT44B0700U (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0306	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
TB0306	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P035-00/ /</b>		<b>ALL</b>
	Z	9	BJ	W1066	39E	22		25-53-16	ALL
	Z	9	BJ	W1066	44C	22		25-53-16	ALL
	Z	9	BJ	W1066	45C	22		25-53-16	ALL
	Z	9	BJ	W1066	46C	22		25-53-16	ALL
	Z	9	BJ	W1066	47C	22		25-53-17	050-099
	Z	9	BJ	W1066	48C	22		25-53-17	050-099
	Z	9	BJ	W1066	49C	22		25-53-17	050-099
	Y	A001	BJ	W1066	37A	22		25-53-15	ALL
	Y	A001	BJ	W1066	40G	22		25-53-15	ALL
	Y	A002	BJ	W1066	37C	22		25-53-15	ALL
	Y	A002	BJ	W1066	41G	22		25-53-15	ALL
	Y	A003	BJ	W1066	37D	22		25-53-15	ALL
	Y	A003	BJ	W1066	42G	22		25-53-15	ALL
	Y	A004	BJ	W1066	37F	22		25-53-15	ALL
	Y	A004	BJ	W1066	43G	22		25-53-15	ALL
	Y	A006	BJ	W1066	02G	22		25-53-14	150-199, 275-299
	Y	A006	BJ	W1066	02J	22		25-53-16	050-099
	Y	A006	BJ	W1066	37S	22		25-53-17	ALL
	Y	A006	BJ	W1066	50G	22		25-53-17	ALL
	Y	C001	BJ	W1066	03C	22		25-53-16	ALL
	Y	C001	BJ	W1066	37K	22		25-53-16	ALL
	Y	C001	BJ	W1066	44G	22		25-53-16	ALL
	Y	C002	BJ	W1066	03L	22		25-53-16	050-099
	Y	C002	BJ	W1066	04H	22		25-53-16	050-099
	Y	C002	BJ	W1066	795	22		25-53-16	050-099
	Y	C002	BJ	W1066	887	22		25-53-16	050-099
	Y	C004	BJ	W1066	02Q	22		25-53-14	050-099
	Y	C004	BJ	W1066	197	22		25-53-14	050-099
	Y	C004	BJ	W1066	37M	22		25-53-17	150-199, 275-299
	Y	C004	BJ	W1066	47G	22		25-53-17	150-199, 275-299
	Y	C004	BJ	W1066	858	22		25-53-14	050-099
	Y	C005	BJ	W1066	196	22		25-53-14	050-099
	Y	C005	BJ	W1066	35T	22		25-53-14	050-099
	Y	C005	BJ	W1066	37N	22		25-53-17	150-199, 275-299
	Y	C005	BJ	W1066	48G	22		25-53-17	150-199, 275-299
	Y	C005	BJ	W1066	533	22		25-53-14	050-099
	Y	C006	BJ	W1066	37P	22		25-53-17	ALL
	Y	C006	BJ	W1066	49G	22		25-53-17	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 18

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0307</b>		<b>BACT44A0580D</b>					<b>0163/204/R021</b>		<b>ALL</b>
<b>TB0307</b>	<b>F</b>	<b>BACM15C1A</b>					<b>0163/204/R021</b>		<b>ALL</b>
<b>TB0307</b>	<b>G</b>	<b>BACM15C1B</b>					<b>0165/200/R020</b>		<b>ALL</b>
	G	11	2	W0445	WBB	22		23-51-21	ALL
	G	11	2	W0445	WBV	22		23-51-21	ALL
	G	11	2	W0631	003	24		23-51-21	ALL
	F	A001	2	W0445	WKY	22		22-11-32	ALL
	F	A001	2	W0483	004	22		22-11-32	ALL
	F	A002	2	W0445	WYL	22		22-11-12	ALL
	F	A002	2	W0481	004	22		22-11-12	ALL
	F	A003	2	W0445	WBU	22		22-11-12	ALL
	F	A003	2	W0481	006	22		22-11-12	ALL
	F	A004	2	W0445	WBL	22		22-11-22	ALL
	F	A004	2	W0485	004	22		22-11-22	ALL
	F	A005	2	W0445	WOR	22		27-41-21	ALL
	F	A005	2	W1283	011	20		27-41-21	ALL
	F	A006	2	W0445	WBK	22		27-41-21	ALL
	F	A006	2	W1281	009	20		27-41-21	ALL
	F	A007	2	W0445	WRD	22		27-41-21	ALL
	F	A007	2	W1281	011	20		27-41-21	ALL
	F	A008	2	W0445	WGY	22		23-51-21	ALL
	F	A008	2	W0631	002	24		23-51-21	ALL
	F	C001	2	W0445	WBG	22		22-11-32	ALL
	F	C001	2	W0483	006	22		22-11-32	ALL
	F	C002	2	W0445	WHT	22		22-11-12	ALL
	F	C002	2	W0481	005	22		22-11-12	ALL
	F	C003	2	W0445	WGR	22		22-11-12	ALL
	F	C003	2	W0481	007	22		22-11-12	ALL
	F	C004	2	W0445	WBN	22		22-11-22	ALL
	F	C004	2	W0485	005	22		22-11-22	ALL
	F	C005	2	W0445	WVI	22		27-41-21	ALL
	F	C005	2	W1283	010	20		27-41-21	ALL
	F	C006	2	W0445	WBO	22		27-41-21	ALL
	F	C006	2	W1281	010	20		27-41-21	ALL
	F	C008	2	W0445	WBR	22		23-51-21	ALL
	F	C008	2	W0631	004	24		23-51-21	ALL
<b>TB0308</b>		<b>BACT44B0700U</b>					<b>P039-00/ /</b>		<b>ALL</b>
<b>TB0308</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P039-00/ /</b>		<b>ALL</b>
<b>TB0308</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P039-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W1068	39D	22		25-53-26	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0300

Page 19

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0308		<b>BACT44B0700U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0308	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
TB0308	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	Z	10	BJ	W1068	44E	22		25-53-26	ALL
	Z	10	BJ	W1068	45E	22		25-53-26	ALL
	Z	10	BJ	W1068	46E	22		25-53-26	ALL
	Z	10	BJ	W1068	47E	22		25-53-27	050-099, 150-199
	Z	10	BJ	W1068	48E	22		25-53-27	050-099, 150-199
	Z	10	BJ	W1068	49E	22		25-53-27	050-099, 150-199
	Z	11	BJ	W1068	179	22		25-53-26	050-099
	Z	11	BJ	W1068	37V	22		25-53-26	ALL
	Z	11	BJ	W1068	44B	22		25-53-26	ALL
	Z	11	BJ	W1068	45B	22		25-53-26	ALL
	Z	11	BJ	W1068	46B	22		25-53-26	ALL
	Z	11	BJ	W1068	47B	22		25-53-27	050-099, 150-199
	Z	11	BJ	W1068	48B	22		25-53-27	050-099, 150-199
	Z	11	BJ	W1068	49B	22		25-53-27	050-099, 150-199
	Z	12	BJ	W1068	180	22		25-53-25	ALL
	Z	12	BJ	W1068	40B	22		25-53-25	ALL
	Z	12	BJ	W1068	41B	22		25-53-25	ALL
	Z	12	BJ	W1068	42B	22		25-53-25	ALL
	Z	12	BJ	W1068	43B	22		25-53-25	ALL
	Z	13	BJ	W1068	37J	22		25-53-26	050-099
	Z	13	BJ	W1068	37L	22		25-53-26	050-099
	Z	13	BJ	W1068	46G	22		25-53-26	050-099
	Z	13	BJ	W1068	806	22		25-53-26	050-099
	Z	13	BJ	W1068	843	22		25-53-26	050-099
	Z	7	BJ	W1068	38D	22		25-53-25	ALL
	Z	7	BJ	W1068	40E	22		25-53-25	ALL
	Z	7	BJ	W1068	41E	22		25-53-25	ALL
	Z	7	BJ	W1068	42E	22		25-53-25	ALL
	Z	7	BJ	W1068	43E	22		25-53-25	ALL
	Z	8	BJ	W1068	178	22		25-53-27	150-199
	Z	8	BJ	W1068	37T	22		25-53-23	ALL
	Z	8	BJ	W1068	37U	22		25-53-23	ALL
	Z	8	BJ	W1068	38E	22		25-53-25	ALL
	Z	8	BJ	W1068	40C	22		25-53-25	ALL
	Z	8	BJ	W1068	41C	22		25-53-25	ALL
	Z	8	BJ	W1068	42C	22		25-53-25	ALL
	Z	8	BJ	W1068	43C	22		25-53-25	ALL
	Z	9	BJ	W1068	37U	22		25-53-23	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 20

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0308</b>		<b>BACT44B0700U (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
<b>TB0308</b>	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
<b>TB0308</b>	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P039-00/ /</b>		<b>ALL</b>
	Z	9	BJ	W1068	39E	22		25-53-26	ALL
	Z	9	BJ	W1068	44C	22		25-53-26	ALL
	Z	9	BJ	W1068	45C	22		25-53-26	ALL
	Z	9	BJ	W1068	46C	22		25-53-26	ALL
	Z	9	BJ	W1068	47C	22		25-53-27	050-099, 150-199
	Z	9	BJ	W1068	48C	22		25-53-27	050-099, 150-199
	Z	9	BJ	W1068	49C	22		25-53-27	050-099, 150-199
	Y	A001	BJ	W1068	37A	22		25-53-25	ALL
	Y	A001	BJ	W1068	40G	22		25-53-25	ALL
	Y	A002	BJ	W1068	37C	22		25-53-25	ALL
	Y	A002	BJ	W1068	41G	22		25-53-25	ALL
	Y	A003	BJ	W1068	37D	22		25-53-25	ALL
	Y	A003	BJ	W1068	42G	22		25-53-25	ALL
	Y	A004	BJ	W1068	37F	22		25-53-25	ALL
	Y	A004	BJ	W1068	43G	22		25-53-25	ALL
	Y	C001	BJ	W1068	181	22		25-53-26	050-099
	Y	C001	BJ	W1068	37K	22		25-53-26	050-099
	Y	C001	BJ	W1068	44G	22		25-53-26	050-099
	Y	C001	BJ	W1068	826	22		25-53-26	050-099
	Y	C002	BJ	W1068	182	22		25-53-26	ALL
	Y	C002	BJ	W1068	45G	22		25-53-26	150-199, 275-299
	Y	C002	BJ	W1068	728	22		25-53-26	050-099
	Y	C002	BJ	W1068	754	22		25-53-26	050-099
	Y	C004	BJ	W1068	37M	22		25-53-27	050-099, 150-199
	Y	C004	BJ	W1068	47G	22		25-53-27	050-099, 150-199
	Y	C005	BJ	W1068	37N	22		25-53-27	050-099, 150-199
	Y	C005	BJ	W1068	48G	22		25-53-27	050-099, 150-199
	Y	C006	BJ	W1068	37P	22		25-53-27	050-099, 150-199
	Y	C006	BJ	W1068	37R	22		25-53-27	050-099, 150-199
	Y	C006	BJ	W1068	49G	22		25-53-27	050-099, 150-199
<b>TB0310</b>		<b>BACM15C3B</b>					<b>P065-00/ /</b>		<b>ALL</b>
<b>TB0310</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P065-00/ /</b>		<b>ALL</b>
<b>TB0310</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P065-00/ /</b>		<b>ALL</b>
	Z	1	BJ	W2058	001	22		24-25-11	ALL
	Z	1	BJ	W2058	002	22		24-25-11	ALL
	Z	1	BJ	W2058	003	22		24-25-11	ALL
	Z	1	BJ	W2058	053	22		24-25-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 21

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0310</b>		<b>BACM15C3B (continued)</b>					<b>P065-00/ /</b>		<b>ALL</b>
<b>TB0310</b>	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P065-00/ /</b>		<b>ALL</b>
<b>TB0310</b>	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P065-00/ /</b>		<b>ALL</b>
	Z	1	BJ	W2058	061	22		24-25-11	ALL
	Y	A004	BJ	W2058	022	22		24-25-11	ALL
	Y	A004	BJ	W2058	030	22		24-25-11	ALL
	Y	A004	BJ	W2058	042	22		24-25-11	ALL
	Y	A006	BJ	W2058	030	22		24-25-11	ALL
	Y	A006	BJ	W2058	048	22		24-25-11	ALL
	Y	A006	BJ	W2058	050	22		24-25-11	ALL
	Y	A010	BJ	W2058	005	22		24-25-11	ALL
	Y	A010	BJ	W2058	007	22		24-25-11	ALL
	Y	A010	BJ	W2058	008	22		24-25-11	ALL
<b>TB0314</b>		<b>BACT44B0405U</b>					<b>P037-00/ /</b>		<b>050-099, 162-199, 275-299</b>
<b>TB0314</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0314</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0314</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	5	BJ	W0192	71X	20		36-11-62	050-099, 155-156, 162-166, 276
	Z	5	BJ	W0192	71X	20		36-11-52	150-154, 275
	Z	5	BJ	W0192	71Y	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	5	BJ	W0192	72A	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	5	BJ	W0192	72B	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	5	BJ	W0192	72C	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	6	BJ	W0192	65T	24		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	6	BJ	W0192	71A	22		36-11-52	050-099, 150-156, 162-166, 275-276
	Z	6	BJ	W0192	71B	22		36-11-52	050-099, 150-156, 162-166, 275-276
	Z	6	BJ	W0192	71C	22		36-11-52	050-099, 150-156, 162-166, 275-276
	Z	6	BJ	W0192	71L	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	6	BJ	W0192	71M	22		36-11-62	050-099, 150-156, 162-166, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 22

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0314		<b>BACT44B0405U (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 162-199, 275-299</b>
TB0314	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0314	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0314	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	6	BJ	W0192	71N	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	6	BJ	W0192	71P	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Z	7	BJ	W0188	11F	24		21-28-11	050-099, 155-199, 275-299
	Z	7	BJ	W1118	11V	24		21-26-31	150-154, 275
	Z	7	BJ	W1118	12K	24		21-28-11	ALL
	Z	7	BJ	W1118	12Y	24		21-28-11	ALL
	Z	7	BJ	W1118	13C	24		21-28-11	ALL
	Z	7	BJ	W1118	13F	22		21-26-31	050-099, 155-199, 276-299
	Z	7	BJ	W1118	547	22		21-26-31	ALL
	Y	A003	BJ	W0192	041	22		36-11-52	ALL
	Y	A003	BJ	W0192	71F	22		36-11-52	050-099, 150-156, 162-166, 275-276
	Y	A003	BJ	W0192	71G	20		36-11-52	ALL
	Y	A003	BJ	W0192	72F	20		36-11-52	ALL
	Y	A004	BJ	W0192	24A	22		36-11-62	ALL
	Y	A004	BJ	W0192	71R	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	A004	BJ	W0192	71S	20		36-11-62	ALL
	Y	A004	BJ	W0192	71W	22		36-11-62	ALL
	Y	A005	BJ	W0192	061	24		36-11-62	157, 167-199, 277-299
	Y	A005	BJ	W0192	65U	24		36-11-62	157, 167-199, 277-299
	Y	A005	BJ	W0192	65Y	24		36-11-62	157, 167-199, 277-299
	X	A009	BJ	W0188	11D	22		21-28-11	050-099, 150-199, 275-276
	X	A009	BJ	W1118	11Y	22		21-28-11	050-099, 150-199, 275-276
	X	B009	BJ	W0188	11E	22		21-28-11	050-099, 150-199, 275-276
	X	B009	BJ	W1118	13D	22		21-28-11	050-099, 150-199, 275-276
	Y	C003	BJ	W0192	040	22		36-11-52	ALL
	Y	C003	BJ	W0192	71H	22		36-11-52	050-099, 150-156, 162-166, 275-276
	Y	C003	BJ	W0192	71J	20		36-11-52	ALL
	Y	C003	BJ	W0192	71K	20		36-11-52	ALL
	Y	C004	BJ	W0192	049	20		36-11-62	157, 167-199, 277-299
	Y	C004	BJ	W0192	26A	22		36-11-62	050-099, 150-156, 162-166, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 23

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0314		<b>BACT44B0405U (continued)</b>					<b>P037-00/ /</b>		<b>050-099, 162-199, 275-299</b>
TB0314	X	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0314	Y	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0314	Z	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	C004	BJ	W0192	71T	22		36-11-62	050-099, 150-156, 162-166, 275-276
	Y	C004	BJ	W0192	71U	20		36-11-62	ALL
	Y	C004	BJ	W0192	71V	22		36-11-62	ALL
	X	C009	BJ	W0192	70C	22		21-28-11	ALL
	X	C009	BJ	W1118	70A	22		21-28-11	ALL
	Z	CAP	Y	W1118	11X	24		21-26-31	ALL
	X	DED		W0192	70CZ			21-28-11	050-099
	X	DED		W1118	11YZ			21-28-11	050-099
	X	DED		W1118	13DZ			21-28-11	050-099
	X	DED		W1118	70AZ			21-28-11	050-099
TB0318		<b>BACT44B1200U</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	D	<b>DIODEBLOCK-REF284T0187-</b>					<b>P036-00/ /</b>		<b>050-099, 162-199</b>
TB0318	D	<b>DIODEBLOCK-REF284T0187-</b>					<b>P036-00/ /</b>		<b>150, 152-157</b>
TB0318	F	<b>BACM15C1A</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	G	<b>BACM15C1B</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	H	<b>BACM15C2A</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	X	<b>BACM15C3A</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	Y	<b>BACM15C3B</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	Z	<b>BACM15C3C</b>					<b>P036-00/ /</b>		<b>ALL</b>
	Z			W0176	22WZ			78-34-11	ALL
	X			W0176	28E	20		21-66-21	050-099, 162-199
	X			W0176	39FZ			21-66-11	050-099, 162-199
	X			W0176	40FZ			21-66-21	050-099, 162-199
	X			W0176	41FZ			21-66-41	050-099, 150, 152-199
	X			W0176	42F	20		21-66-11	050-099, 162-199
	X			W0176	43EZ			21-66-31	050-099, 150, 152-199
	X			W0176	43F	20		21-66-41	050-099, 150, 152-199
	X			W0176	64E	20		21-66-31	050-099, 150, 152-199
	Z			W0176	67HZ			78-34-11	ALL
	Z			W0176	84J	20		78-34-11	ALL
	G	22	2	W0182	153	18		38-32-14	277-299
	G	22	2	W0182	154	18		38-32-14	277-299
	G	22	2	W0182	155	20		38-32-14	277-299
	Z	29	BJ	W0176	22W	20		78-34-11	ALL
	Z	29	BJ	W0176	67H	20		78-34-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 24

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0318		BACT44B1200U (continued)					P036-00/ /		ALL
TB0318	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		050-099, 162-199
TB0318	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		150, 152-157
TB0318	F	BACM15C1A (continued)					P036-00/ /		ALL
TB0318	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0318	H	BACM15C2A (continued)					P036-00/ /		ALL
TB0318	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0318	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0318	Z	BACM15C3C (continued)					P036-00/ /		ALL
	Z	29	BJ	W0176	67J	24		78-34-11	ALL
	Z	29	BJ	W0176	809	24		78-34-11	ALL
	Z	32	BJ	W0176	26A	22		21-66-11	050-099, 162-199
	Z	32	BJ	W0176	27A	22		21-66-11	050-099, 162-199
	Z	32	BJ	W0176	27A	22		21-66-41	150, 152-157
	Z	32	BJ	W0176	34E	22		21-66-31	050-099, 150, 152-199
	Z	32	BJ	W0176	41F	22		21-66-21	050-099, 162-199
	Z	32	BJ	W0176	65E	22		21-66-41	050-099, 150, 152-199
	H	33	2	W0176	18K	22		73-21-11	ALL
	H	33	2	W0176	18M	22		73-21-11	ALL
	H	33	2	W0176	18V	20		73-21-11	ALL
	H	33	2	W0176	18Y	16		73-21-11	ALL
	H	33	2	W0176	19R	16		73-21-11	ALL
	D	A001	2	W0176	94A	22		21-66-11	050-099, 162-199
	D	A002	2	W0176	66A	22		21-66-11	050-099, 162-199
	D	A002	2	W0176	68A	22		21-66-11	050-099, 162-199
	D	A003	2	W0176	21B	22		21-66-11	050-099, 162-199
	D	A003	2	W0176	22B	22		21-66-11	050-099, 162-199
	D	A004	2	W0176	65A	22		21-66-11	050-099, 162-199
	D	A004	2	W0176	66A	22		21-66-11	050-099, 162-199
	D	A005	2	W0176	49A	22		21-66-11	050-099, 162-199
	D	A006	2	W0176	22E	22		21-66-21	050-099, 162-199
	D	A007	2	W0176	44E	22		21-66-31	050-099, 150, 152-199
	D	A008	2	W0176	44F	22		21-66-41	050-099, 150, 152-199
	X	A009	BJ	W0176	39FR	22		21-66-11	050-099, 162-199
	X	A010	BJ	W0176	39FB	22		21-66-11	050-099, 162-199
	X	A011	BJ	W0056	065	20		21-66-11	050-099, 162-199
	X	A011	BJ	W0176	22A	20		21-66-11	050-099, 162-199
	Y	A016	BJ	W0176	18L	20		73-21-11	150-199, 275-276
	Y	A016	BJ	W0176	18R	20		73-21-11	150-199, 275-276
	Y	A016	BJ	W0176	18S	20		73-21-11	150-199, 275-276

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 25

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0318		BACT44B1200U (continued)					P036-00/ /		ALL
TB0318	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		050-099, 162-199
TB0318	D	DIODEBLOCK-REF284T0187- (continued)					P036-00/ /		150, 152-157
TB0318	F	BACM15C1A (continued)					P036-00/ /		ALL
TB0318	G	BACM15C1B (continued)					P036-00/ /		ALL
TB0318	H	BACM15C2A (continued)					P036-00/ /		ALL
TB0318	X	BACM15C3A (continued)					P036-00/ /		ALL
TB0318	Y	BACM15C3B (continued)					P036-00/ /		ALL
TB0318	Z	BACM15C3C (continued)					P036-00/ /		ALL
	Y	A016	BJ	W0176	18U	20		73-21-11	150-199, 275-276
	Y	A017	BJ	W0176	285R	24		77-12-11	050-099, 162-199, 277-299
	Y	A017	BJ	W0176	287R	24		77-12-11	050-099, 162-199, 277-299
	Y	A018	BJ	W0176	285B	24		77-12-11	050-099, 162-199, 277-299
	Y	A018	BJ	W0176	287B	24		77-12-11	050-099, 162-199, 277-299
	Y	A019	BJ	W0176	249B	24		77-31-11	050-099, 162-199, 277-299
	Y	A019	BJ	W0176	270B	24		77-12-12	050-099, 162-199, 277-299
	Y	A019	BJ	W0176	271B	24		77-12-12	050-099, 162-199, 277-299
	Y	A020	BJ	W0176	249R	24		77-31-11	050-099, 162-199, 277-299
	Y	A020	BJ	W0176	270R	24		77-12-12	050-099, 162-199, 277-299
	Y	A020	BJ	W0176	271R	24		77-12-12	050-099, 162-199, 277-299
	X	A035	BJ	W0056	064	22		21-66-11	050-099, 162-199
	X	A035	BJ	W0176	21A	22		21-66-11	050-099, 162-199
	X	A036	BJ	W0056	079	22		21-66-31	050-099, 150, 152-199
	X	A036	BJ	W0176	45E	22		21-66-31	050-099, 150, 152-199
	X	B009	BJ	W0176	40FR	22		21-66-21	050-099, 162-199
	X	B010	BJ	W0176	40FB	22		21-66-21	050-099, 162-199
	X	B011	BJ	W0056	066	20		21-66-11	050-099, 162-199
	X	B011	BJ	W0176	23A	20		21-66-11	050-099, 162-199
	X	B035	BJ	W0056	070	20		21-66-11	050-099, 162-199
	X	B035	BJ	W0176	32A	20		21-66-11	050-099, 162-199
	D	C001	2	W0176	78A	22		21-66-11	050-099, 162-199
	D	C001	2	W0176	95A	22		21-66-11	050-099, 162-199
	D	C002	2	W0176	23B	22		21-66-11	050-099, 162-199
	D	C002	2	W0176	69A	22		21-66-11	050-099, 162-199
	D	C003	2	W0176	23B	22		21-66-11	050-099, 162-199
	D	C004	2	W0176	78A	22		21-66-11	050-099, 162-199
	D	C005	2	W0176	67A	22		21-66-11	050-099, 162-199
	D	C006	2	W0176	23E	22		21-66-21	050-099, 162-199
	D	C006	2	W0176	25E	22		21-66-21	050-099, 162-199
	D	C007	2	W0176	25E	22		21-66-21	050-099, 162-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 26

Feb 06/2009

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0318		<b>BACT44B1200U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 162-199</b>
TB0318	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>150, 152-157</b>
TB0318	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	D	C007	2	W0176	26E	22		21-66-21	050-099, 162-199
	D	C007	2	W0176	44C	22		21-66-41	150, 152-157
	D	C007	2	W0180	181	22		21-66-41	150, 152-157
	D	C008	2	W0176	26E	22		21-66-21	050-099, 162-199
	D	C008	2	W0176	44C	22		21-66-41	150, 152-157
	X	C009	BJ	W0176	43ER	22		21-66-31	050-099, 150, 152-199
	X	C010	BJ	W0176	43EB	22		21-66-31	050-099, 150, 152-199
	X	C011	BJ	W0056	067	20		21-66-11	050-099, 162-199
	X	C011	BJ	W0176	25A	20		21-66-11	050-099, 162-199
	X	C012	BJ	W0056	084	22		21-66-11	164-199
	X	C012	BJ	W0176	39A	22		21-66-11	164-199
	Y	C015	BJ	W0176	47F	22		36-11-61	157, 167-199, 277-299
	Y	C015	BJ	W0176	48F	22		36-11-61	157, 167-199, 277-299
	Y	C015	BJ	W0176	802	24		36-11-61	157, 167-199, 277-299
	Y	C017	BJ	W0176	285Z			77-12-11	050-099, 162-199, 277-299
	Y	C017	BJ	W0176	287Z			77-12-11	050-099, 162-199, 277-299
	Y	C019	BJ	W0176	249Z			77-31-11	050-099, 162-199, 277-299
	Y	C019	BJ	W0176	270Z			77-12-12	050-099, 277-299
	Y	C019	OJ	W0176	270Z			77-12-12	162-199
	Y	C019	BJ	W0176	271Z			77-12-12	050-099, 162-199, 277-299
	X	C035	BJ	W0056	071	20		21-66-11	050-099, 162-199
	X	C035	BJ	W0176	33A	20		21-66-11	050-099, 162-199
	Y	CAP	Y	W0184	218B	24		77-12-11	050-099, 162-165
	Y	CAP	Y	W0184	218B	24		77-12-11	166-199, 277-299
	Y	CAP	Y	W0184	218R	24		77-12-11	050-099, 166-199, 277-299
	Y	CAP	Y	W0184	218R	24		77-12-11	162-165
	X	D009	BJ	W0176	41FR	22		21-66-41	050-099, 150, 152-199
	X	D010	BJ	W0176	41FB	22		21-66-41	050-099, 150, 152-199
	X	D035	BJ	W0056	072	20		21-66-11	050-099, 162-199
	X	D035	BJ	W0176	34A	20		21-66-11	050-099, 162-199
	X	D036	BJ	W0176	62T	24		21-43-11	ALL

### TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 27

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0318		<b>BACT44B1200U (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>050-099, 162-199</b>
TB0318	<b>D</b>	<b>DIODEBLOCK-REF284T0187- (continued)</b>					<b>P036-00/ /</b>		<b>150, 152-157</b>
TB0318	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>H</b>	<b>BACM15C2A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
TB0318	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
	X	D036	BJ	W0182	550	24		21-43-11	ALL
	H	DED		W0176	18KZ			73-21-11	ALL
	H	DED		W0176	18MZ			73-21-11	ALL
	Y	DED		W0184	218Z			77-12-11	050-099, 162-199, 277-299
<b>TB0320</b>		<b>BACT44B1200U</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0320</b>	<b>D</b>	<b>DIODEBLOCK-REF284T0188-</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0320</b>	<b>F</b>	<b>BACM15C1A</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0320</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0320</b>	<b>R</b>	<b>RESISTORBLOCK-REF284T0188-</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0320</b>	<b>X</b>	<b>BACM15C3A</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0320</b>	<b>Y</b>	<b>BACM15C3B</b>					<b>P037-00/ /</b>		<b>ALL</b>
<b>TB0320</b>	<b>Z</b>	<b>BACM15C3C</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Z	22	BJ	W0192	08Q	22		30-21-11	050-099, 150-199
	Z	22	BJ	W0192	81F	22		30-21-11	050-099, 150-199
	Z	22	BJ	W0192	81G	22		30-21-11	050-099, 150-199
	Z	22	BJ	W0192	81J	22		30-21-11	050-099, 150-199
	Z	22	BJ	W0192	81K	22		30-21-11	050-099, 150-199
	X	A001	BJ	W0188	094	24		30-21-11	050-099, 150-199
	X	A001	BJ	W0192	81X	22		30-21-11	050-099
	X	A001	BJ	W0192	81X	24		30-21-11	150-199
	D	A003	2	W1118	13F	22		21-26-31	050-099, 155-199, 276-299
	D	A004	2	W1118	540	24		21-43-11	050-099, 155-199, 276-299
	D	A004	2	W1118	546	24		21-43-11	050-099, 155-199, 276-299
	X	A005	BJ	W0058	072	22		21-66-21	050-099, 162-199
	X	A005	BJ	W0192	73Y	22		21-66-21	050-099, 162-199
	F	A007	2	W0058	082	18		21-66-41	050-099, 150, 152-199
	F	A007	2	W0192	75D	18		21-66-41	050-099, 150, 152-199
	F	A008	2	W0058	074	18		21-66-21	050-099, 162-199
	F	A008	2	W0192	74B	18		21-66-21	050-099, 162-199
	Y	A009	BJ	W0192	0AI	22		36-11-62	157, 167-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 28

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0320		BACT44B1200U (continued)					P037-00/ /		ALL
TB0320	D	DIODEBLOCK-REF284T0188- (continued)					P037-00/ /		ALL
TB0320	F	BACM15C1A (continued)					P037-00/ /		ALL
TB0320	G	BACM15C1B (continued)					P037-00/ /		ALL
TB0320	R	RESISTORBLOCK-REF284T0188- (continued)					P037-00/ /		ALL
TB0320	X	BACM15C3A (continued)					P037-00/ /		ALL
TB0320	Y	BACM15C3B (continued)					P037-00/ /		ALL
TB0320	Z	BACM15C3C (continued)					P037-00/ /		ALL
	Y	A009	BJ	W0192	0AJ	22		36-11-62	157, 167-199, 277-299
	Y	A009	BJ	W0192	682	24		36-11-62	157, 167-199, 277-299
	Y	A010	BJ	W0192	75I	22		21-66-41	050-099, 150, 152-199
	Y	A010	BJ	W0192	75N	22		21-66-41	050-099, 150, 152-199
	Y	A010	BJ	W0192	75R	22		21-66-41	050-099, 150, 152-199
	Y	A011	BJ	W0192	01Y	20		30-71-24	051-099, 155-199
	Y	A011	BJ	W0192	54X	20		30-71-24	051-099
	Y	A011	BJ	W0192	59N	20		30-71-24	051-099
	Y	A011	BJ	W1118	092	20		30-71-24	155-199
	Y	A011	BJ	W1118	094	20		30-71-24	155-199
	Y	A012	BJ	W0192	83G	22		30-81-11	050-099, 150-199
	Y	A012	BJ	W0192	83H	22		30-21-11	050-099, 150-199
	Y	A012	BJ	W0192	841	22		30-21-11	050-099, 150-199
	Y	A019	BJ	W0192	0AE	22		36-11-62	156-157, 166-199, 277-299
	Y	A019	BJ	W0192	0AF	22		36-11-62	156-157, 166-199, 277-299
	Y	A019	BJ	W0192	680	22		36-11-62	156-157, 166-199, 277-299
	Y	A019	BJ	W0192	72D	22		36-11-62	156, 166
	Y	A020	BJ	W0192	19Y	24		73-21-18	ALL
	Y	A020	BJ	W0192	83D	24		73-21-18	ALL
	Y	A020	BJ	W0192	83F	24		73-21-18	ALL
	R	A029	2	W0192	22XB	22		21-61-81	050-099, 155-199, 275-299
	R	A029	BJ	W0192	22XB	22		21-61-81	151-154
	F	A030	2	W0192	22VR	22		21-61-81	050-099, 155-199, 275-299
	F	A030	BJ	W0192	22VR	22		21-61-81	151-154
	F	A030	2	W0192	22YR	22		21-61-81	050-099, 155-199, 275-299
	F	A030	BJ	W0192	22YR	22		21-61-81	151-154
	R	A031	2	W0192	22YB	22		21-61-81	050-099, 155-199, 275-299
	R	A031	BJ	W0192	22YB	22		21-61-81	151-154
	D	A032	2	W0192	80E	24		21-61-81	050-099, 155-199, 275-299
	D	A032	BJ	W0192	80E	24		21-61-81	151-154
	Y	A033	BJ	W0188	013	24		21-61-21	ALL
	Y	A033	BJ	W0192	04X	24		21-61-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0300

Page 29

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0320		<b>BACT44B1200U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>R</b>	<b>RESISTORBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	Y	A033	BJ	W0192	08W	24		21-61-21	ALL
	Y	A034	BJ	W0192	72H	24		21-61-81	050-099, 151-199, 275-299
	Y	A034	BJ	W0192	80D	24		21-61-81	050-099, 151-199, 275-299
	Y	A034	BJ	W0192	80G	24		21-61-81	050-099, 151-199, 275-299
	X	A036	BJ	W0188	270Z			32-45-12	275-299
	X	A036	BJ	W0192	273Z			32-45-12	275-299
	X	B005	BJ	W0058	077	22		21-66-21	050-099, 162-199
	X	B005	BJ	W0192	75A	22		21-66-21	050-099, 162-199
	X	B036	BJ	W0188	271R	20		32-45-12	275-299
	X	B036	BJ	W0198	200R	20		32-45-12	275-299
	D	C003	2	W1118	11V	24		21-26-31	050-099, 155-199, 276-299
	D	C004	2	W1118	541	24		21-43-11	050-099, 155-199, 276-299
	X	C005	BJ	W0058	078	20		21-66-21	050-099, 162-199
	X	C005	BJ	W0192	75B	20		21-66-21	050-099, 162-199
	X	C006	BJ	W0192	83K	20		SPARE	280-299
	X	C006	BJ	W1118	562	20		SPARE	280-299
	F	C007	2	W0058	073	18		21-66-21	050-099, 162-199
	F	C007	2	W0192	74A	18		21-66-21	050-099, 162-199
	F	C008	2	W0058	075	18		21-66-21	050-099, 162-199
	F	C008	2	W0192	74C	18		21-66-21	050-099, 162-199
	Y	C009	BJ	W0192	0AK	24		36-21-11	156-162, 166-199, 277-299
	Y	C009	BJ	W0192	0AL	24		36-21-11	156-162, 166-199, 277-299
	Y	C009	BJ	W0192	526	24		36-21-11	156-157, 166-199, 277-299
	Y	C012	BJ	W0188	043	22		28-31-12	050
	Y	C012	BJ	W0192	66W	22		28-31-12	050
	Y	C012	BJ	W0192	66X	22		28-31-12	050
	Y	C019	BJ	W0192	0AG	22		36-11-62	156-157, 166-199, 277-299
	Y	C019	BJ	W0192	0AH	22		36-11-62	156-157, 166-199, 277-299
	Y	C019	BJ	W0192	681	22		36-11-62	156-157, 166-199, 277-299
	Y	C019	BJ	W0192	72E	22		36-11-62	156, 166
	R	C029	2	W0192	22WB	22		21-61-81	050-099, 155-199, 275-299
	R	C029	BJ	W0192	22WB	22		21-61-81	151-154

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 30

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL	Diagram	Effectivity
		Term					CO		
TB0320		<b>BACT44B1200U (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>D</b>	<b>DIODEBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>G</b>	<b>BACM15C1B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>R</b>	<b>RESISTORBLOCK-REF284T0188- (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>X</b>	<b>BACM15C3A (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>Y</b>	<b>BACM15C3B (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
TB0320	<b>Z</b>	<b>BACM15C3C (continued)</b>					<b>P037-00/ /</b>		<b>ALL</b>
	F	C030	2	W0192	22WR	22		21-61-81	050-099, 155-199, 275-299
	F	C030	BJ	W0192	22WR	22		21-61-81	151-154
	F	C030	2	W0192	22XR	22		21-61-81	050-099, 155-199, 275-299
	F	C030	BJ	W0192	22XR	22		21-61-81	151-154
	R	C031	2	W0192	22VB	22		21-61-81	050-099, 155-199, 275-299
	R	C031	BJ	W0192	22VB	22		21-61-81	151-154
	D	C032	2	W0192	80F	24		21-61-81	050-099, 155-199, 275-299
	D	C032	BJ	W0192	80F	24		21-61-81	151-154
	Y	C033	BJ	W0188	014	24		21-61-21	050-099, 280-299
	Y	C033	BJ	W0192	08V	24		21-61-21	050-099, 280-299
	Y	C033	BJ	W0192	568	24		21-61-21	050-099, 280-299
	X	C035	BJ	W0188	270R	20		32-45-12	275-299
	X	C035	BJ	W0192	273R	20		32-45-12	275-299
	X	C036	BJ	W0188	271B	20		32-45-12	275-299
	X	C036	BJ	W0198	200B	20		32-45-12	275-299
	X	D005	BJ	W0058	079	20		21-66-21	050-099, 162-199
	X	D005	BJ	W0192	75C	20		21-66-21	050-099, 162-199
	X	D006	BJ	W0198	622	20		SPARE	280-299
	X	D006	BJ	W1118	563	20		SPARE	280-299
	X	D035	BJ	W0188	270B	20		32-45-12	275-299
	X	D035	BJ	W0192	273B	20		32-45-12	275-299
	X	D036	BJ	W0188	271Z			32-45-12	275-299
	X	D036	BJ	W0198	200Z			32-45-12	275-299
	Y	DED		W0188	043Z			28-31-12	050
	Y	DED		W0192	66WZ			28-31-12	050
	Y	DED		W0192	66XZ			28-31-12	050
		DED		W0198	622Z			SPARE	280-299
<b>TB0322</b>		<b>284T0384</b>					<b>0331/173/L048</b>		<b>150-199, 275-299</b>
<b>TB0322</b>	<b>F</b>	<b>BACM15C1A</b>					<b>0331/173/L048</b>		<b>150-199, 275-299</b>
	F			W0622	201Z			30-41-11	ALL
	F			W0622	202Z			30-41-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 31

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0322		<b>284T0384 (continued)</b>					<b>0331/173/L048</b>		<b>150-199, 275-299</b>
TB0322	F	<b>BACM15C1A (continued)</b>					<b>0331/173/L048</b>		<b>150-199, 275-299</b>
	F			W0622	203Z			30-41-11	ALL
	F			W0622	204Z			30-41-11	ALL
	F			W0622	205Z			30-41-11	ALL
	F			W0622	206Z			30-41-11	ALL
	F			W0622	212Z			30-41-11	ALL
	F			W0622	213Z			30-41-11	ALL
	F			W0622	214Z			30-41-11	ALL
	F	A001	2	W0622	205B	24		30-41-11	ALL
	F	A002	2	W0622	206B	24		30-41-11	ALL
	F	A002	2	W0622	212B	24		30-41-11	ALL
	F	A003	2	W0622	203B	24		30-41-11	ALL
	F	A004	2	W0622	204B	24		30-41-11	ALL
	F	A004	2	W0622	213B	24		30-41-11	ALL
	F	A005	2	W0622	201B	24		30-41-11	ALL
	F	A006	2	W0622	202B	24		30-41-11	ALL
	F	A006	2	W0622	214B	24		30-41-11	ALL
	F	C001	2	W0622	205R	24		30-41-11	ALL
	F	C002	2	W0622	206R	24		30-41-11	ALL
	F	C002	2	W0622	212R	24		30-41-11	ALL
	F	C003	2	W0622	203R	24		30-41-11	ALL
	F	C004	2	W0622	204R	24		30-41-11	ALL
	F	C004	2	W0622	213R	24		30-41-11	ALL
	F	C005	2	W0622	201R	24		30-41-11	ALL
	F	C006	2	W0622	202R	24		30-41-11	ALL
	F	C006	2	W0622	214R	24		30-41-11	ALL
TB0324		<b>284T0384</b>					<b>0331/173/R044</b>		<b>150-199, 275-299</b>
TB0324	F	<b>BACM15C1A</b>					<b>0331/173/R044</b>		<b>150-199, 275-299</b>
	F			W0624	202Z			30-41-12	ALL
	F			W0624	203Z			30-41-12	ALL
	F			W0624	204Z			30-41-12	ALL
	F			W0624	205Z			30-41-12	ALL
	F			W0624	206Z			30-41-12	ALL
	F			W0624	209Z			30-41-12	ALL
	F			W0624	215Z			30-41-12	ALL
	F			W0624	216Z			30-41-12	ALL
	F			W0624	217Z			30-41-12	ALL
	F	A001	2	W0624	202B	24		30-41-12	ALL
	F	A002	2	W0624	203B	24		30-41-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0300

Page 32

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0324</b>		<b>284T0384 (continued)</b>					<b>0331/173/R044</b>		<b>150-199, 275-299</b>
<b>TB0324</b>	<b>F</b>	<b>BACM15C1A (continued)</b>					<b>0331/173/R044</b>		<b>150-199, 275-299</b>
	F	A002	2	W0624	215B	24		30-41-12	ALL
	F	A003	2	W0624	204B	24		30-41-12	ALL
	F	A004	2	W0624	205B	24		30-41-12	ALL
	F	A004	2	W0624	216B	24		30-41-12	ALL
	F	A005	2	W0624	206B	24		30-41-12	ALL
	F	A006	2	W0624	209B	24		30-41-12	ALL
	F	A006	2	W0624	217B	24		30-41-12	ALL
	F	C001	2	W0624	202R	24		30-41-12	ALL
	F	C002	2	W0624	203R	24		30-41-12	ALL
	F	C002	2	W0624	215R	24		30-41-12	ALL
	F	C003	2	W0624	204R	24		30-41-12	ALL
	F	C004	2	W0624	205R	24		30-41-12	ALL
	F	C004	2	W0624	216R	24		30-41-12	ALL
	F	C005	2	W0624	206R	24		30-41-12	ALL
	F	C006	2	W0624	209R	24		30-41-12	ALL
	F	C006	2	W0624	217R	24		30-41-12	ALL
<b>TB0336</b>	<b>Y</b>	<b>BACM15C3E</b>					<b>P101-00/ /</b>		<b>ALL</b>

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0300

Page 33 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB0450</b>		<b>BACT44B0400U</b>					<b>220/166/R055</b>		<b>150-154, 275-276</b>
<b>TB0450</b>	<b>D</b>	<b>DIODEBLOCK</b>					<b>P089-00/ /</b>		<b>150-154, 275-276</b>
<b>TB0450</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P089-00/ /</b>		<b>150-154, 275-276</b>
	G	2	2	W0892	005	20		28-31-22	150-154, 275
	G	2	2	W0892	009	22		28-31-22	150-154, 275
	G	2	2	W0892	011	22		28-31-22	150-154, 275
	G	3	2	W0892	013	22		28-31-22	150-154, 275
	G	3	2	W0892	020	22		28-31-22	150-154, 275
	G	3	2	W0894	021	22		28-31-22	150-154, 275
	D	A001	2	W0892	036	22		28-31-22	150-154, 275
	D	A001	2	W0892	037	22		28-31-22	150-154, 275
	D	C001	2	W0892	031	22		28-31-22	150-154, 275
	D	C001	2	W0892	035	22		28-31-22	150-154, 275
	G	DED		W0892	013Z			28-31-22	150-154, 275
	G	DED		W0892	020Z			28-31-22	150-154, 275
	D	DED		W0892	031Z			28-31-22	150-154, 275
	D	DED		W0892	035Z			28-31-22	150-154, 275
	D	DED		W0892	036Z			28-31-22	150-154, 275
	D	DED		W0892	037Z			28-31-22	150-154, 275
	G	DED		W0894	021Z			28-31-22	150-154, 275
<b>TB0452</b>		<b>BACT44B0400U</b>					<b>220/166/R055</b>		<b>150-154, 275-276</b>
<b>TB0452</b>	<b>D</b>	<b>DIODEBLOCK</b>					<b>P089-00/ /</b>		<b>150-154, 275-276</b>
<b>TB0452</b>	<b>G</b>	<b>BACM15C1B</b>					<b>P089-00/ /</b>		<b>150-154, 275-276</b>
	G	4	2	W0894	005	20		28-31-22	150-154, 275
	G	4	2	W0894	009	22		28-31-22	150-154, 275
	G	4	2	W0894	011	22		28-31-22	150-154, 275
	D	A001	2	W0892	037	22		28-31-22	150-154, 275
	D	A001	2	W0894	036	22		28-31-22	150-154, 275
	D	A002	2	W0894	038	22		28-31-22	150-154, 275
	D	A003	2	W0894	051	22		28-31-22	150-154, 275
	D	C001	2	W0894	031	22		28-31-22	150-154, 275
	D	C001	2	W0894	035	22		28-31-22	150-154, 275
	D	C002	2	W0894	049	22		28-31-22	150-154, 275
	D	C002	2	W0894	050	22		28-31-22	150-154, 275
	D	C003	2	W0894	050	22		28-31-22	150-154, 275
	D	DED		W0892	037Z			28-31-22	150-154, 275
	D	DED		W0894	031Z			28-31-22	150-154, 275
	D	DED		W0894	035Z			28-31-22	150-154, 275
	D	DED		W0894	036Z			28-31-22	150-154, 275

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0400

Page 1

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0454		BACT44B0600U					P087-00/ /		278-299
TB0456		BACT44B0700U					P087-00/ /		278-299
TB0456	Y	BACM15C3B					P087-00/ /		ALL
TB0456	Z	BACM15C3C					P087-00/ /		ALL
TB0458	D	DIODEBLOCK-REF284T0189-					P033-00/ /		ALL
TB0458	X	BACM15C3A					P033-00/ /		ALL
TB0458	Y	BACM15C3B					P033-00/ /		ALL
TB0458	Z	BACM15C3C					P033-00/ /		ALL
	Z			W0140	015Z			78-34-11	ALL
	Z			W0140	017Z			78-34-11	ALL
	Z			W0140	026Z			78-34-11	ALL
	Y			W0140	028Z			78-34-11	ALL
	Y			W0140	030Z			78-34-11	ALL
	Y			W0140	034	20		78-34-11	ALL
	Z			W0140	167Z			78-34-11	ALL
	Z			W0140	168Z			78-34-11	ALL
	Z			W0140	176	20		78-34-11	ALL
	Y			W0144	838Z			78-34-11	ALL
	Y			W0144	839Z			78-34-11	ALL
	Y			W0144	840	20		78-34-11	ALL
	Z			W0144	879Z			78-34-11	ALL
	Z			W0144	882	20		78-34-11	ALL
	Z	7	BJ	W0140	015	20		78-34-11	ALL
	Z	7	BJ	W0140	017	20		78-34-11	ALL
	Z	7	BJ	W0140	026	20		78-34-11	ALL
	Z	7	BJ	W0140	167	20		78-34-11	ALL
	Z	7	BJ	W0140	168	20		78-34-11	ALL
	Z	7	BJ	W0144	879	20		78-34-11	ALL
	Z	8	BJ	W0140	183	24		78-36-11	ALL
	Z	8	BJ	W0144	664	24		78-36-11	ALL
	Z	8	BJ	W0144	756	24		78-36-11	ALL
	Z	8	BJ	W0144	855	22		78-36-11	ALL
	X	A001	BJ	W0140	013	22		78-34-11	ALL
	X	A001	BJ	W0144	834	22		78-34-11	ALL
	D	A003	2	W0140	033	20		78-34-11	ALL
	D	A004	2	W0140	032	20		78-34-11	ALL
	Y	A005	BJ	W0144	754	22		78-36-11	ALL
	Y	A005	BJ	W0144	820	22		78-36-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0400

Page 2

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity	
TB0458	D	<b>DIODEBLOCK-REF284T0189- (continued)</b>						<b>P033-00/ /</b>		<b>ALL</b>
TB0458	X	<b>BACM15C3A (continued)</b>						<b>P033-00/ /</b>		<b>ALL</b>
TB0458	Y	<b>BACM15C3B (continued)</b>						<b>P033-00/ /</b>		<b>ALL</b>
TB0458	Z	<b>BACM15C3C (continued)</b>						<b>P033-00/ /</b>		<b>ALL</b>
	Y	A005	BJ	W0144	880	22		78-36-11	ALL	
	Y	A006	BJ	W0140	029	20		78-34-11	ALL	
	Y	A006	BJ	W0140	030	20		78-34-11	ALL	
	Y	A006	BJ	W0144	838	20		78-34-11	ALL	
	X	A009	BJ	W0140	182	24		78-36-11	ALL	
	X	A009	BJ	W0144	744	24		78-36-11	ALL	
	X	A010	BJ	W0140	180	24		78-36-11	ALL	
	X	A010	BJ	W0144	735	24		78-36-11	ALL	
	D	A013	2	W0144	841	22		78-36-11	ALL	
	D	A014	2	W0144	851	22		78-36-11	ALL	
	X	B001	BJ	W0140	011	22		78-34-11	ALL	
	X	B001	BJ	W0144	833	22		78-34-11	ALL	
	X	B009	BJ	W0140	177	24		78-36-11	ALL	
	X	B009	BJ	W0144	725	24		78-36-11	ALL	
	X	C001	BJ	W0140	004	20		78-34-11	ALL	
	X	C001	BJ	W0144	878	20		78-34-11	ALL	
	X	C002	BJ	W0140	013Z			78-34-11	ALL	
	X	C002	BJ	W0144	834Z			78-34-11	ALL	
	D	C003	2	W0140	031	20		78-34-11	ALL	
	D	C004	2	W0140	029	20		78-34-11	ALL	
	Y	C005	BJ	W0140	001	20		78-34-11	ALL	
	Y	C005	BJ	W0140	005	20		78-34-11	ALL	
	Y	C005	BJ	W0140	018	20		78-34-11	ALL	
	Y	C005	BJ	W0146	065	20		78-34-11	ALL	
	Y	C006	BJ	W0140	028	20		78-34-11	ALL	
	Y	C006	BJ	W0140	031	20		78-34-11	ALL	
	Y	C006	BJ	W0144	839	20		78-34-11	ALL	
	X	C009	BJ	W0140	178	24		78-36-11	ALL	
	X	C009	BJ	W0144	734	24		78-36-11	ALL	
	D	C013	2	W0140	181	24		78-36-11	ALL	
	D	C013	2	W0144	729	24		78-36-11	ALL	
	D	C014	2	W0140	179	24		78-36-11	ALL	
	D	C014	2	W0144	742	24		78-36-11	ALL	
	Y	DED		W0140	001Z			78-34-11	ALL	
	Y	DED		W0140	005Z			78-34-11	ALL	
	Y	DED		W0140	018Z			78-34-11	ALL	
	X	DED		W0140	177Z			78-36-11	ALL	

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0400

Page 3

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0458	D	<b>DIODEBLOCK-REF284T0189- (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0458	X	<b>BACM15C3A (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0458	Y	<b>BACM15C3B (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0458	Z	<b>BACM15C3C (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
	X	DED		W0140	178Z			78-36-11	ALL
	D	DED		W0140	179Z			78-36-11	ALL
	X	DED		W0140	180Z			78-36-11	ALL
	D	DED		W0140	181Z			78-36-11	ALL
	X	DED		W0140	182Z			78-36-11	ALL
	Z	DED		W0140	183Z			78-36-11	ALL
	X	DED		W0144	725Z			78-36-11	ALL
	D	DED		W0144	729Z			78-36-11	ALL
	X	DED		W0144	734Z			78-36-11	ALL
	X	DED		W0144	735Z			78-36-11	ALL
	D	DED		W0144	742Z			78-36-11	ALL
	X	DED		W0144	744Z			78-36-11	ALL
	Y	DED		W0146	065Z			78-34-11	ALL
TB0460	D	<b>DIODEBLOCK</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0460	X	<b>BACM15C3A</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0460	Y	<b>BACM15C3B</b>					<b>P033-00/ /</b>		<b>ALL</b>
TB0460	Z	<b>BACM15C3C</b>					<b>P033-00/ /</b>		<b>ALL</b>
	Z			W0136	026Z			78-34-21	ALL
	Z			W0136	027Z			78-34-21	ALL
	Z			W0136	043Z			78-34-21	ALL
	Z			W0136	045Z			78-34-21	ALL
	Y			W0136	050Z			78-34-21	ALL
	Y			W0136	051	20		78-34-21	ALL
	Y			W0136	052Z			78-34-21	ALL
	Z			W0136	070Z			78-34-21	ALL
	Z			W0136	073	20		78-34-21	ALL
	Z			W0142	12GZ			78-34-21	ALL
	Y			W0142	12HZ			78-34-21	ALL
	Y			W0142	12JZ			78-34-21	ALL
	Y			W0142	12K	20		78-34-21	ALL
	Z			W0142	13Q	20		78-34-21	ALL
	Z	7	BJ	W0136	081	24		78-36-21	ALL
	Z	7	BJ	W0142	02F	24		78-36-21	ALL
	Z	7	BJ	W0142	11L	24		78-36-21	ALL
	Z	7	BJ	W0142	11W	24		78-36-21	ALL
	Z	7	BJ	W0142	13K	22		78-36-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0400

Page 4

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0460	D	DIODEBLOCK (continued)					P033-00/ /		ALL
TB0460	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0460	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0460	Z	BACM15C3C (continued)					P033-00/ /		ALL
	Z	8	BJ	W0136	026	20		78-34-21	ALL
	Z	8	BJ	W0136	027	20		78-34-21	ALL
	Z	8	BJ	W0136	043	20		78-34-21	ALL
	Z	8	BJ	W0136	045	20		78-34-21	ALL
	Z	8	BJ	W0136	070	20		78-34-21	ALL
	Z	8	BJ	W0142	12G	20		78-34-21	ALL
	X	A001	BJ	W0136	040	20		78-34-21	ALL
	X	A001	BJ	W0142	12E	20		78-34-21	ALL
	D	A003	2	W0136	055	20		78-34-21	ALL
	D	A004	2	W0136	054	20		78-34-21	ALL
	Y	A006	BJ	W0136	049	20		78-34-21	ALL
	Y	A006	BJ	W0136	050	20		78-34-21	ALL
	Y	A006	BJ	W0142	12H	20		78-34-21	ALL
	X	A009	BJ	W0136	076	24		78-36-21	ALL
	X	A009	BJ	W0142	11V	24		78-36-21	ALL
	X	A010	BJ	W0136	080	24		78-36-21	ALL
	X	A010	BJ	W0142	11P	24		78-36-21	ALL
	D	A013	2	W0142	13N	22		78-36-21	ALL
	D	A014	2	W0142	13M	22		78-36-21	ALL
	X	B001	BJ	W0136	042	20		78-34-21	ALL
	X	B001	BJ	W0142	12F	20		78-34-21	ALL
	X	B009	BJ	W0136	077	24		78-36-21	ALL
	X	B009	BJ	W0142	11N	24		78-36-21	ALL
	X	C001	BJ	W0136	018	20		78-34-21	ALL
	X	C001	BJ	W0142	13P	20		78-34-21	ALL
	X	C002	BJ	W0136	040Z			78-34-21	ALL
	X	C002	BJ	W0142	12EZ			78-34-21	ALL
	D	C003	2	W0136	049	20		78-34-21	ALL
	D	C004	2	W0136	053	20		78-34-21	ALL
	Y	C005	BJ	W0136	015	20		78-34-21	ALL
	Y	C005	BJ	W0136	019	20		78-34-21	ALL
	Y	C005	BJ	W0136	024	20		78-34-21	ALL
	Y	C005	BJ	W0146	064	20		78-34-21	ALL
	Y	C006	BJ	W0136	052	20		78-34-21	ALL
	Y	C006	BJ	W0136	053	20		78-34-21	ALL
	Y	C006	BJ	W0142	12J	20		78-34-21	ALL
	X	C009	BJ	W0136	078	24		78-36-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB0400

Page 5

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TB0460	D	DIODEBLOCK (continued)					P033-00/ /		ALL
TB0460	X	BACM15C3A (continued)					P033-00/ /		ALL
TB0460	Y	BACM15C3B (continued)					P033-00/ /		ALL
TB0460	Z	BACM15C3C (continued)					P033-00/ /		ALL
	X	C009	BJ	W0142	11T	24		78-36-21	ALL
	D	C013	2	W0136	075	24		78-36-21	ALL
	D	C013	2	W0142	11M	24		78-36-21	ALL
	D	C014	2	W0136	079	24		78-36-21	ALL
	D	C014	2	W0142	11R	24		78-36-21	ALL
	Y	DED		W0136	015Z			78-34-21	ALL
	Y	DED		W0136	019Z			78-34-21	ALL
	Y	DED		W0136	024Z			78-34-21	ALL
	Y	DED		W0146	064Z			78-34-21	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB0400

Page 6 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Part Number		Type	Bundle	Wire No.	GA	Station / WL / BL		
	Fix	Term					CO	Diagram	Effectivity
<b>TB5002</b>		<b>MS27212-3-3</b>					<b>P006-03/ /</b>		<b>ALL</b>
		1	F4	W0210	001	04		24-51-11	ALL
		1	F	W1024	001	08		24-51-11	ALL
		1	F	W1024	004	08		24-51-11	ALL
		1	F	W1024	065	14		24-51-11	ALL
		2	F4	W0210	002	04		24-51-11	ALL
		2	F	W1024	002	08		24-51-11	ALL
		2	F	W1024	005	08		24-51-11	ALL
		2	F	W1024	064	14		24-51-11	ALL
		3	F4	W0210	003	04		24-51-11	ALL
		3	F	W1024	003	08		24-51-11	ALL
		3	F	W1024	006	08		24-51-11	ALL
		3	F	W1024	063	14		24-51-11	ALL
<b>TB5008</b>		<b>MS27212-2-3</b>					<b>P006-04/ /</b>		<b>ALL</b>
		1	E/	W0212	001	06		24-51-21	ALL
		1	E	W1028	010	08		24-51-21	ALL
		1	E	W1028	053	14		24-51-21	050-099, 153-199, 275-299
		1	E	W1028	053	18		24-51-21	150-152
		2	E/	W0212	002	06		24-51-21	ALL
		2	E	W1028	011	08		24-51-21	ALL
		2	E	W1028	052	14		24-51-21	050-099, 153-199, 275-299
		2	E	W1028	052	18		24-51-21	150-152
		3	E/	W0212	003	06		24-51-21	ALL
		3	E	W1028	012	08		24-51-21	ALL
		3	E	W1028	051	14		24-51-21	050-099, 153-199, 275-299
		3	E	W1028	051	18		24-51-21	150-152
<b>TB5010</b>		<b>MS27212-3-5</b>					<b>P006-02/ /</b>		<b>ALL</b>
		1	F	W0266	001	02		24-32-11	ALL
		1	F	W1032	001	06		24-32-11	ALL
		2	F	W0268	001	02		24-32-11	ALL
		2	F	W1036	001	06		24-32-11	ALL
		3	F	W1030	057	06		25-29-12	ALL
		3	F	W1220	006	06		25-29-12	ALL
		4	F	W0272	10W	08		24-54-21	ALL
		4	F	W1030	056	08		24-54-21	ALL
		4	F	W1030	062	08		24-54-21	050-099, 150-152, 162-199, 275-299
		4	F	W1036	004	08		24-54-21	ALL
		5	F	W0210	03P	08		24-54-11	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5000

Page 1

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5010</b>		<b>MS27212-3-5 (continued)</b>					<b>P006-02/ /</b>		<b>ALL</b>
		5	F	W1026	084	08		24-54-11	ALL
<b>TB5012</b>		<b>MS27212-1-3</b>					<b>P006-00/ /</b>		<b>ALL</b>
		1	C	W1026	032	14		24-33-11	ALL
		1	C	W1040	025	16		24-33-11	ALL
		1	C	W1040	026	14		24-33-11	ALL
		2	C	W1026	035	18		24-33-11	ALL
		2	C	W1040	027	18		24-33-11	ALL
		2	C	W1040	028	18		24-33-11	ALL
		3	C	W1026	085	12		24-54-73	ALL
		3	C	W1040	017	12		24-54-73	ALL
		3	C	W1040	059	12		24-54-73	ALL
<b>TB5014</b>		<b>MS27212-4-3-MS27212-4-1</b>					<b>P006-01/ /</b>		<b>ALL</b>
		1	Q	W0258	001	*1		24-31-11	ALL
		1	Q	W1042	001	06		24-31-11	ALL
		1	Q	W1042	003	06		24-31-11	050-099, 150-154, 162-163, 275-276
		1	Q	W1042	005	06		24-31-11	155-157, 164-199, 277-299
		1	Q	W1042	009	06		24-31-11	050-099, 150-154, 162-163, 275-276
		2	G	W0218	005	04		24-31-11	ALL
		2	G	W1040	001	06		24-31-11	ALL
		3	G	W1040	040	08		29-21-31	ALL
		3	G	W1208	001	08		29-21-31	ALL
		4	Q	W1042	010	06		24-31-11	ALL
		4	G	W1338	016	06		24-31-11	ALL
<b>TB5020</b>		<b>MS27212-2-16</b>					<b>P011-00/280/0000</b>		<b>ALL</b>
		1	E	W0036	001	12		24-51-11	ALL
		1	E	W0036	005	12		24-51-11	ALL
		1	E	W0276	001	12		24-51-11	ALL
		10	E	W0032	103	14		24-54-73	ALL
		10	E	W0278	004	14		24-54-73	ALL
		11	E	W0032	090	12		24-54-73	ALL
		11	E	W0278	001	12		24-54-73	ALL
		12	E	W0036	036	12		24-51-42	ALL
		12	E	W0036	127	12		24-51-42	ALL
		12	E	W0276	013	12		24-51-42	ALL
		13	E	W0044	734	24		24-51-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5000

Page 2

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5020</b>		<b>MS27212-2-16 (continued)</b>					<b>P011-00/280/0000</b>		<b>ALL</b>
		13	E	W0278	005	24		24-51-31	ALL
		15	E	W0032	011	08		24-54-71	ALL
		15	E	W0032	012	08		24-54-71	ALL
		16	E	W0038	115	20		24-51-43	ALL
		16	E	W0038	117	20		24-51-43	ALL
		16	E	W0280	013	20		24-51-43	ALL
		2	E	W0036	003	12		24-51-11	ALL
		2	E	W0036	006	12		24-51-11	ALL
		2	E	W0276	002	12		24-51-11	ALL
		3	E	W0036	115	12		24-51-11	ALL
		3	E	W0276	003	12		24-51-11	ALL
		4	E	W0036	022	16		24-51-11	ALL
		4	E	W0036	029	12		24-51-11	050-099
		4	E	W0036	029	16		24-51-11	150-199, 275-299
		4	E	W0276	004	12		24-51-11	ALL
		5	E	W0036	025	16		24-51-11	150-199, 275-276
		5	E	W0036	030	16		24-51-11	ALL
		5	E	W0036	198	16		24-51-11	050-099, 277-299
		5	E	W0276	005	12		24-51-11	ALL
		6	E	W0036	026	16		24-51-11	ALL
		6	E	W0036	033	16		24-51-11	ALL
		6	E	W0276	006	12		24-51-11	ALL
		7	E	W0036	077	10		24-54-11	ALL
		7	E	W0036	080	10		24-54-11	ALL
		7	E	W0276	007	10		24-54-11	ALL
		8	E	W0036	052	08		24-54-11	ALL
		8	E	W0036	058	08		24-54-11	ALL
		8	E	W0276	008	08		24-54-11	ALL
		9	E	W0036	041	14		24-53-11	ALL
		9	E	W0036	044	14		24-53-11	ALL
		9	E	W0276	009	10		24-53-11	ALL
<b>TB5022</b>		<b>MS27212-2-16</b>					<b>0218/286/R015</b>		<b>ALL</b>
		1	E	W0038	037	14		24-51-52	ALL
		1	E	W0038	095	12		24-51-52	ALL
		1	E	W0280	001	12		24-51-52	ALL
		10	E	W0038	038	14		24-53-21	ALL
		10	E	W0038	099	14		24-53-21	ALL
		10	E	W0280	004	10		24-53-21	ALL
		11	E	W0038	032	22		24-51-31	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5000

Page 3

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5022</b>		<b>MS27212-2-16 (continued)</b>					<b>0218/286/R015</b>		<b>ALL</b>
		11	E	W0278	003	22		24-51-31	ALL
		12	E	W0038	034	18		24-51-31	ALL
		12	E	W0278	002	18		24-51-31	ALL
		13	E	W0032	001	08		24-54-71	ALL
		13	E	W0032	011	08		24-54-71	ALL
		13	E	W0032	031	08		24-54-71	ALL
		13	E	W0278	006	08		24-54-71	ALL
		14	E	W0038	112	20		24-51-42	ALL
		14	E	W0276	014	20		24-51-42	ALL
		15	E	W0038	113	20		24-51-42	ALL
		15	E	W0276	015	20		24-51-42	ALL
		16	E	W0038	114	20		24-51-42	ALL
		16	E	W0276	016	20		24-51-42	ALL
		2	E	W0038	001	12		24-51-21	ALL
		2	E	W0038	003	12		24-51-21	ALL
		2	E	W0280	005	12		24-51-21	ALL
		3	E	W0038	010	12		24-51-21	ALL
		3	E	W0280	006	12		24-51-21	ALL
		4	E	W0038	009	12		24-51-21	ALL
		4	E	W0280	007	12		24-51-21	ALL
		5	E	W0038	016	16		24-51-21	ALL
		5	E	W0038	024	16		24-51-21	ALL
		5	E	W0280	008	14		24-51-21	ALL
		6	E	W0038	019	16		24-51-21	ALL
		6	E	W0038	028	16		24-51-21	ALL
		6	E	W0280	009	14		24-51-21	ALL
		7	E	W0038	021	16		24-51-21	ALL
		7	E	W0038	031	16		24-51-21	ALL
		7	E	W0280	010	14		24-51-21	ALL
		8	E	W0038	045	08		24-54-21	ALL
		8	E	W0038	056	08		24-54-21	ALL
		8	E	W0280	002	08		24-54-21	ALL
		9	E	W0038	059	08		24-54-21	ALL
		9	E	W0038	063	08		24-54-21	ALL
		9	E	W0038	077	08		24-54-21	ALL
		9	E	W0280	003	08		24-54-21	ALL
		DED		W0038	032Z			24-51-31	ALL
		DED		W0038	034Z			24-51-31	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB5000

Page 4

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Part Number		Type	Bundle	Wire No.	GA	Station / WL / BL		
	Fix	Term					CO	Diagram	Effectivity
<b>TB5032</b>		<b>MS27212-2-6</b>					<b>P031-00/ /</b>		<b>ALL</b>
		1	E	W0296	001	08		24-51-12	ALL
		1	E	W1016	004	08		24-51-12	ALL
		2	E	W0296	002	08		24-51-12	ALL
		2	E	W1016	005	08		24-51-12	ALL
		3	E	W0296	003	08		24-51-12	ALL
		3	E	W1016	006	08		24-51-12	ALL
<b>TB5034</b>		<b>MS27212-2-6</b>					<b>P032-00/ /</b>		<b>ALL</b>
		1	E/	W0238	010	06		24-32-41	275-299
		1	E	W1020	017	08		24-32-41	275-299
		2	E/	W0238	009	06		24-32-41	275-299
		2	E	W1020	018	08		24-32-41	275-299
		3	E/	W0238	008	06		24-32-41	275-299
		3	E	W1020	019	08		24-32-41	275-299
		4	E	W0298	001	08		24-51-22	ALL
		4	E	W1020	004	08		24-51-22	ALL
		5	E	W0298	002	08		24-51-22	ALL
		5	E	W1020	005	08		24-51-22	ALL
		6	E	W0298	003	08		24-51-22	ALL
		6	E	W1020	006	08		24-51-22	ALL
<b>TB5076</b>		<b>MS27212-1-14</b>					<b>P036-00/ /</b>		<b>ALL</b>
		10	C	W0056	005	12		23-34-18	ALL
		10	C	W0176	592	12		23-34-18	ALL
		11	C	W0056	002	16		23-34-16	ALL
		11	C	W0176	575	16		23-34-16	ALL
		12	C	W0056	011	12		30-41-11	ALL
		12	C	W0182	203B	12		30-41-11	ALL
		13	C	W0056	012	12		30-41-11	ALL
		13	C	W0182	203R	12		30-41-11	ALL
		5	C	W0056	024	12		38-32-11	ALL
		5	C	W0182	200	12		38-32-11	ALL
		6	C	W0056	025	12		38-32-11	ALL
		6	C	W0182	201	12		38-32-11	ALL
		7	C	W0056	026	12		38-32-11	ALL
		7	C	W0182	202	12		38-32-11	ALL
		8	C	W0056	001	16		23-34-15	ALL
		8	C	W0176	553	16		23-34-15	ALL
		9	C	W0056	004	12		23-34-18	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5000

Page 5

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5076</b>		<b>MS27212-1-14 (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
		9	C	W0176	591	12		23-34-18	ALL
<b>TB5078</b>		<b>MS27212-1-14</b>					<b>P037-00/ /</b>		<b>ALL</b>
		1	C	W0058	201B	12		30-41-12	ALL
		1	C	W1118	202B	12		30-41-12	ALL
		10	C	W0058	017	12		21-25-21	ALL
		10	C	W1118	099	12		21-25-21	ALL
		11	C	W0058	005	12		24-51-24	ALL
		11	C	W0192	062	12		24-51-24	ALL
		2	C	W0058	201R	12		30-41-12	ALL
		2	C	W1118	202R	12		30-41-12	ALL
		5	C	W0058	001	12		38-32-11	ALL
		5	C	W1118	066	12		38-32-11	ALL
		6	C	W0058	002	12		38-32-11	ALL
		6	C	W1118	067	12		38-32-11	ALL
		7	C	W0058	003	12		38-32-11	ALL
		7	C	W1118	068	12		38-32-11	ALL
		8	C	W0058	015	12		21-25-21	ALL
		8	C	W1118	097	12		21-25-21	ALL
		9	C	W0058	016	12		21-25-21	ALL
		9	C	W1118	098	12		21-25-21	ALL
<b>TB5096</b>		<b>MS27212-2-12</b>					<b>P033-00/ /</b>		<b>ALL</b>
		1	E	W0052	060	12		24-51-52	ALL
		1	E	W0142	792	12		24-51-52	ALL
		10	N	W0138	001	08		24-51-52	ALL
		10	N2	W0138	004	10		24-51-52	ALL
		10	N2	W0138	005	10		24-51-52	ALL
		10	N2	W0138	070	10		24-51-52	050-099, 275-299
		10	N1	W0138	070	12		24-51-52	150-199
		10	N2	W0138	073	10		24-51-52	050-099, 275-299
		10	N1	W0138	073	10		24-51-52	150-199
		11	N	W0138	002	08		24-51-52	ALL
		11	N2	W0138	018	10		24-51-52	ALL
		11	N2	W0138	019	10		24-51-52	ALL
		11	N1	W0138	074	10		24-51-52	ALL
		11	N1	W0138	101	14		24-51-52	ALL
		12	N	W0138	003	08		24-51-52	ALL
		12	N2	W0138	027	10		24-51-52	ALL
		12	N2	W0138	031	10		24-51-52	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5000

Page 6

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5096</b>		<b>MS27212-2-12 (continued)</b>					<b>P033-00/ /</b>		<b>ALL</b>
		12	N2	W0138	032	10		24-51-52	ALL
		12	N2	W0138	075	10		24-51-52	ALL
		2	E	W0052	061	12		24-51-52	ALL
		2	E	W0142	793	12		24-51-52	ALL
		3	E	W0052	062	12		24-51-52	ALL
		3	E	W0142	794	12		24-51-52	ALL
		4	E	W0052	028	12		24-51-52	ALL
		4	E	W0142	773	12		24-51-52	ALL
		6	E	W0052	025	18		25-29-11	ALL
		6	E	W0142	797	18		25-29-11	ALL
		7	E	W0052	091	12		23-34-17	280-299
		7	E	W0142	23A	12		23-34-17	280-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**  
Section TB5000  
Page 7 End  
Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5100</b>		<b>MS27212-2-2</b>					<b>0223/260/L052</b>		<b>ALL</b>
		=G	E	W0632	038	20		33-14-31	ALL
		=G	E	W0632	B-B			33-14-31	ALL
		=P	E	W0632	037	24		33-14-31	ALL
		=P	E	W0632	B-A			33-14-31	ALL
<b>TB5102</b>		<b>MS27212-2-2</b>					<b>0165/215/L053</b>		<b>ALL</b>
		=G	E	W0632	040	20		33-14-31	ALL
		=G	E	W0632	C-B			33-14-31	ALL
		=P	E	W0632	039	24		33-14-31	ALL
		=P	E	W0632	C-A			33-14-31	ALL
<b>TB5104</b>		<b>MS27212-2-2</b>					<b>0164/220/R045</b>		<b>ALL</b>
		=G	E	W0632	042	20		33-14-31	ALL
		=G	E	W0632	D-B			33-14-31	ALL
		=P	E	W0632	041	24		33-14-31	ALL
		=P	E	W0632	D-A			33-14-31	ALL
<b>TB5108</b>		<b>MS27212-2-2</b>					<b>0262/285/R007</b>		<b>ALL</b>
<b>TB5120</b>		<b>MS27212-2-6</b>					<b>P023-00/ /</b>		<b>ALL</b>
		1	N	W0678	010	18		33-42-11	ALL
		1	N	W1194	B-D			33-42-11	ALL
		2	N	W0678	011	10		33-42-11	ALL
		2	N	W1194	B-B			33-42-11	ALL
		2	N	W1304	004	10		33-42-11	ALL
		3	N	W1194	B-A			33-42-11	ALL
		3	N	W1304	003	10		33-42-11	ALL
		4	N	W0678	027	18		33-42-21	ALL
		4	N	W1194	D-D			33-42-21	ALL
		5	N	W0678	028	14		33-42-21	ALL
		5	N	W1194	D-B			33-42-21	ALL
		5	N	W1304	008	16		33-42-21	ALL
		6	N	W0678	029	12		33-42-21	ALL
		6	N	W1194	B-F			33-42-11	ALL
		6	N	W1194	D-F			33-42-21	ALL
<b>TB5122</b>		<b>MS27212-2-6</b>					<b>P023-00/ /</b>		<b>ALL</b>
		4	N	W1194	C-A			33-42-21	ALL
		4	N	W1304	005	16		33-42-21	ALL
		5	N	W1194	D-A			33-42-21	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5100

Page 1

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5122</b>		<b>MS27212-2-6 (continued)</b>					<b>P023-00/ /</b>		<b>ALL</b>
		5	N	W1304	007	16		33-42-21	ALL
<b>TB5124</b>		<b>MS27212-2-6</b>					<b>P023-00/ /</b>		<b>ALL</b>
		1	N	W0678	008	18		33-42-11	ALL
		1	N	W1194	A-D			33-42-11	ALL
		2	N	W0678	009	10		33-42-11	ALL
		2	N	W1194	A-B			33-42-11	ALL
		2	N	W1304	002	10		33-42-11	ALL
		3	N	W1194	A-A			33-42-11	ALL
		3	N	W1304	001	10		33-42-11	ALL
		4	N	W0678	026	18		33-42-21	ALL
		4	N	W1194	C-D			33-42-21	ALL
		5	N	W0678	025	14		33-42-21	ALL
		5	N	W1194	C-B			33-42-21	ALL
		5	N	W1304	006	16		33-42-21	ALL
		6	N	W0678	024	10		33-42-11	ALL
		6	N	W1194	A-F			33-42-11	ALL
		6	N	W1194	C-F			33-42-21	ALL
<b>TB5126</b>		<b>MS27212-2-3</b>					<b>R0990/12/RS</b>		<b>ALL</b>
		1	N	W1302	002	20		28-21-12	ALL
		1	N	W1302	A-C			28-21-12	ALL
		2	N	W1302	002Z			28-21-12	ALL
		2	N	W1302	A-B			28-21-12	ALL
		3	N	W1302	001	20		28-21-12	ALL
		3	N	W1302	A-A			28-21-12	ALL
		DED		W1302	001Z			28-21-12	ALL
<b>TB5128</b>		<b>MS27212-2-3</b>					<b>L0990/12/RS</b>		<b>ALL</b>
		1	N	W1300	002	20		28-21-12	ALL
		1	N	W1300	A-C			28-21-12	ALL
		2	N	W1300	002Z			28-21-12	ALL
		2	N	W1300	A-B			28-21-12	ALL
		3	N	W1300	001	20		28-21-12	ALL
		3	N	W1300	A-A			28-21-12	ALL
		DED		W1300	001Z			28-21-12	ALL
<b>TB5130</b>		<b>MS27212-2-8</b>					<b>P036-00/ /</b>		<b>ALL</b>
		1	E	W0296	001	08		24-51-12	ALL
		1	N	W1044	007	10		24-51-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5100

Page 2

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5130</b>		<b>MS27212-2-8 (continued)</b>					<b>P036-00/ /</b>		<b>ALL</b>
		1	N	W1044	091	12		24-51-12	155-199, 276-299
		1	N	W1044	101	12		24-51-12	050-099
		2	E	W0296	002	08		24-51-12	ALL
		2	N	W1044	008	10		24-51-12	ALL
		2	N	W1044	034	14		24-51-12	ALL
		2	N	W1044	130	12		24-51-12	155-157, 165-199, 277-299
		3	E	W0296	003	08		24-51-12	ALL
		3	N	W1044	009	10		24-51-12	050-099
		3	N	W1044	009	08		24-51-12	150-199, 275-299
		3	N	W1044	093	12		24-51-12	155-199, 276-299
		3	N	W1044	102	12		24-51-12	050-099
		4	E	W0296	016	08		24-51-13	ALL
		4	N	W1044	010	10		24-51-13	ALL
		4	N	W1044	038	10		24-51-13	050-099
		4	N	W1044	038	12		24-51-13	150-199, 275-299
		4	E	W1044	907	16		24-51-13	150, 153-199
		4	E	W9041	001W	10		24-51-13	150, 152-199
		5	E	W0296	017	08		24-51-13	ALL
		5	N	W1044	011	10		24-51-13	275-299
		5	N	W1044	036	14		24-51-13	ALL
		5	N	W1044	045	10		24-51-13	ALL
		5	E	W1044	908	16		24-51-13	150, 153-199
		5	E	W9041	001B	10		24-51-13	150, 152-199
		6	E	W0296	018	08		24-51-13	ALL
		6	N	W1044	012	10		24-51-13	ALL
		6	N	W1044	088	12		24-51-13	150-199
		6	N	W1044	108	10		24-51-13	050-099
		6	E	W1044	909	16		24-51-13	150, 153-199
		6	E	W9041	001O	10		24-51-13	150, 152-199
		7	E	W0056	01A	08		24-54-11	ALL
		7	E	W0210	03P	08		24-54-11	050-099, 155-157, 164-199, 277-299
		7	C	W0210	03P	08		24-54-11	150-154, 162-163, 275-276
		7	N	W1044	510	10		24-54-11	050-099, 155-156, 162-199
		8	N	W1044	011	10		24-51-13	050-099, 150-199
		8	N	W1044	027	12		24-51-13	150-199
		8	N	W1044	02A	12		24-51-13	275-299
		8	N	W1044	045	10		24-51-13	ALL
		8	N	W1044	107	10		24-51-13	050-099

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5100

Page 3

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5132</b>		<b>MS27212-2-8</b>					<b>P037-00/ /</b>		<b>ALL</b>
		1	E	W0298	001	08		24-51-22	ALL
		1	N	W1046	007	10		24-51-22	ALL
		1	N	W1046	015	12		24-51-22	150-154
		1	N	W1046	048	14		24-51-22	150-154
		1	N	W1046	048	12		24-51-22	275
		1	N	W1046	054	10		24-51-22	275
		1	N	W1046	061	12		24-51-22	050-099, 155-199, 276-299
		2	E	W0298	002	08		24-51-22	ALL
		2	N	W1046	008	10		24-51-22	ALL
		2	N	W1046	030	14		24-51-22	ALL
		2	N	W1046	04A	12		24-51-22	275
		2	N	W1046	062	12		24-51-22	050-099, 155-199, 276-299
		3	E	W0298	003	08		24-51-22	ALL
		3	N	W1046	009	10		24-51-22	ALL
		3	N	W1046	037	10		24-51-22	275
		3	N	W1046	049	12		24-51-22	150-154, 275
		3	N	W1046	063	12		24-51-22	050-099, 155-199, 276-299
		4	E	W0298	019	08		24-51-23	ALL
		4	N	W1046	010	10		24-51-23	ALL
		4	N	W1046	021	10		24-51-23	050-099, 277-299
		4	E	W1046	021	12		24-51-23	150-154, 162-165
		4	N	W1046	021	12		24-51-23	155-157, 166-199
		4	E	W1046	021	10		24-51-23	275-276
		4	N	W1046	032	14		24-51-23	ALL
		5	E	W0298	020	08		24-51-23	ALL
		5	N	W1046	011	10		24-51-23	ALL
		5	N	W1046	024	12		24-51-23	ALL
		6	E	W0298	021	08		24-51-23	ALL
		6	N	W1046	012	10		24-51-23	ALL
		6	N	W1046	028	12		24-51-23	ALL
		7	E	W0192	60B	08		24-54-21	150-157, 275-276
		7	E	W0272	10W	08		24-54-21	ALL
		7	E	W1046	084	08		24-54-21	050-099, 162-165
		7	N	W1046	084	08		24-54-21	166-199, 277-299
<b>TB5152</b>		<b>MS27212-2-10</b>					<b>P011-00/280/0000</b>		<b>ALL</b>
		1	E	W0036	137	12		24-51-14	ALL
		1	E	W0036	148	12		24-51-14	ALL
		1	E	W0276	017	12		24-51-14	ALL
		10	E	W0036	138	12		24-51-14	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5100

Page 4

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5152</b>		<b>MS27212-2-10 (continued)</b>					<b>P011-00/280/0000</b>		<b>ALL</b>
		10	E	W0036	164	12		24-51-14	ALL
		10	E	W0036	185	12		24-51-14	ALL
		10	E	W0276	020	12		24-51-14	ALL
		2	E	W0036	152	18		24-51-14	ALL
		2	E	W0036	153	18		24-51-14	ALL
		2	E	W0276	018	18		24-51-14	ALL
		3	E	W0036	139	12		24-51-14	ALL
		3	E	W0036	150	12		24-51-14	ALL
		3	E	W0036	156	12		24-51-14	ALL
		3	E	W0276	019	12		24-51-14	ALL
		4	E	W0038	137	12		24-51-24	ALL
		4	E	W0280	018	12		24-51-24	ALL
		5	E	W0038	139	12		24-51-24	ALL
		5	E	W0038	141	12		24-51-24	ALL
		5	E	W0280	017	12		24-51-24	ALL
		6	E	W0038	138	18		24-51-24	ALL
		6	E	W0038	142	18		24-51-24	ALL
		6	E	W0280	019	18		24-51-24	ALL
		7	E	W0038	143	12		24-51-24	ALL
		7	E	W0280	020	12		24-51-24	ALL
		8	E	W0036	131	12		24-51-42	ALL
		8	E	W0276	011	12		24-51-42	ALL
		9	E	W0036	126	12		24-51-42	ALL
		9	E	W0276	012	12		24-51-42	ALL
<b>TB5154</b>		<b>MS27212-2-3</b>					<b>P065-00/ /</b>		<b>ALL</b>
		1	E	W2058	062	20		24-25-12	ALL
		1	E	W2058	073	12		24-25-12	ALL
		1	E	W2058	078	12		24-25-12	ALL
		2	E	W2058	063	20		24-25-12	ALL
		2	E	W2058	074	12		24-25-12	ALL
		2	E	W2058	077	12		24-25-12	ALL
		3	E	W2058	064	20		24-25-12	ALL
		3	E	W2058	075	12		24-25-12	ALL
		3	E	W2058	076	12		24-25-12	ALL
<b>TB5196</b>		<b>MS27212-2-6</b>					<b>P087-00/ /</b>		<b>278-299</b>
		1	E	W2108	001	08		24-51-13	278-299
		1	E	W2110	001	12		24-51-13	278-299
		2	E	W2108	002	08		24-51-13	278-299

TERMINAL STRIP LIST

D280T132

91-21-41

Section TB5100

Page 5

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB5196</b>		<b>MS27212-2-6 (continued)</b>					<b>P087-00/ /</b>		<b>278-299</b>
		2	E	W2110	002	12		24-51-13	278-299
		2	E	W2110	007	14		24-51-13	278-299
		3	E	W2108	003	08		24-51-13	278-299
		3	E	W2110	003	12		24-51-13	278-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TB5100

Page 6 End

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TB9001</b>		<b>CUSTOMER</b>					<b>E006-02/ /</b>		<b>150, 153-199</b>
		1	E	W9008	002	06		25-25-23	150, 153-199
		1	E	W9008	017	16		25-25-23	150, 153-199
		1	E	W9008	ZZA04	04		25-25-23	150, 153-199
		1	E	W9008	ZZA08	04		25-25-24	150, 153-199
		2	E	W9008	004	16		25-25-23	150, 153-199
		2	E	W9008	006	16		25-25-23	150, 153-199
		2	E	W9008	016	16		25-25-24	150, 153-199
		3	E	W9008	008	16		25-25-23	150, 153-199
		3	E	W9008	010	16		25-25-24	150, 153-199
		4	E	W9008	012	16		25-25-24	150, 153-199
		4	E	W9008	014	16		25-25-24	150, 153-199
		4	E	W9008	ZZA04	04		25-25-23	150, 153-199
		4	E	W9008	ZZA08	04		25-25-24	150, 153-199

**TERMINAL STRIP LIST**

D280T132

**91-21-41**

Section TB9000

Page 1 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0012		S233T913-1					0192/202/L063		ALL
TS0013		S233T913-1					0192/202/R063		ALL
I TS0014		10-61072-3					0177/198/R032		050-099, 150-199
I TS0014		10-61072-4					0177/198/R032		050-099, 150-199
TS0015		10-61072-3					0177/198/L032		050-099, 150-199
TS0015		10-61072-4					0177/198/L032		050-099, 150-199
TS0016		10-61072-4					0177/198/L032		050-099, 150-199
TS0016		10-61072-3					0177/198/L032		050-099, 150-199
TS0028		S283T011-3					0976/166/0000		ALL
TS0035		S253T404-2					P010-00/ /		ALL
		BLK		W5150	M-B			27-61-15	ALL
		BLK		W5150	N-B			27-61-17	ALL
		BLU		W5150	M-E			27-61-15	ALL
		BLU		W5150	N-E			27-61-17	ALL
		ORG		W5150	M-D			27-61-15	ALL
		ORG		W5150	N-D			27-61-17	ALL
		PUR		W5150	M-F			27-61-15	ALL
		PUR		W5150	N-F			27-61-17	ALL
		RED		W5150	M-A			27-61-15	ALL
		RED		W5150	N-A			27-61-17	ALL
		YEL		W5150	M-C			27-61-15	ALL
		YEL		W5150	N-C			27-61-17	ALL
TS0036		S253T404-2					0171/209/0000		ALL
		BLK		W5150	P-B			27-61-14	ALL
		BLK		W5150	R-B			27-61-13	ALL
		BLU		W5150	P-E			27-61-14	ALL
		BLU		W5150	R-E			27-61-13	ALL
		ORG		W5150	P-D			27-61-14	ALL
		ORG		W5150	R-D			27-61-13	ALL
		PUR		W5150	P-F			27-61-14	ALL
		PUR		W5150	R-F			27-61-13	ALL
		RED		W5150	P-A			27-61-14	ALL
		RED		W5150	R-A			27-61-13	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0000

Page 1

Aug 05/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0036		<b>S253T404-2 (continued)</b>					<b>0171/209/0000</b>		<b>ALL</b>
		YEL		W5150	P-C			27-61-14	ALL
		YEL		W5150	R-C			27-61-13	ALL
TS0037		<b>S253T404-2</b>					<b>0171/209/0000</b>		<b>ALL</b>
		BLK		W5150	S-B			27-61-16	ALL
		BLK		W5150	T-B			27-61-18	ALL
		BLU		W5150	S-E			27-61-16	ALL
		BLU		W5150	T-E			27-61-18	ALL
		ORG		W5150	S-D			27-61-16	ALL
		ORG		W5150	T-D			27-61-18	ALL
		PUR		W5150	S-F			27-61-16	ALL
		PUR		W5150	T-F			27-61-18	ALL
		RED		W5150	S-A			27-61-16	ALL
		RED		W5150	T-A			27-61-18	ALL
		YEL		W5150	S-C			27-61-16	ALL
		YEL		W5150	T-C			27-61-18	ALL
TS0039		<b>MS28034-1</b>					<b>0805/124/L030</b>		<b>ALL</b>
TS0040		<b>MS28034-1</b>					<b>0807/124/R023</b>		<b>ALL</b>
TS0041		<b>625928-2</b>					<b>0879/124/L034</b>		<b>ALL</b>
TS0042		<b>625928-2</b>					<b>0879/124/R044</b>		<b>ALL</b>
TS0051		<b>S332T301-13</b>					<b>APU/ /</b>		<b>ALL</b>
TS0052		<b>S332T301-12</b>					<b>APU/ /</b>		<b>ALL</b>
TS0082		<b>161T1000-83</b>					<b>WHEEL/01/</b>		<b>ALL</b>
TS0083		<b>161T1000-83</b>					<b>WHEEL/02/</b>		<b>ALL</b>
TS0084		<b>161T1000-83</b>					<b>WHEEL/05/</b>		<b>ALL</b>
TS0085		<b>161T1000-83</b>					<b>WHEEL/06/</b>		<b>ALL</b>
TS0086		<b>161T1000-83</b>					<b>WHEEL/03/</b>		<b>ALL</b>
TS0087		<b>161T1000-83</b>					<b>WHEEL/04/</b>		<b>ALL</b>

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0000

Page 2

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0088		161T1000-83					WHEEL/07/		ALL
TS0089		161T1000-83					WHEEL/08/		ALL
TS0090		S271T451-1					1060/125/R003		ALL
TS0091		S283T002-8					WHEEL/01/L GR		ALL
TS0092		S283T002-8					WHEEL/02/L GR		ALL
TS0093		S283T002-8					WHEEL/05/L GR		ALL
TS0094		S283T002-8					WHEEL/06/L GR		ALL
TS0095		S283T002-8					WHEEL/03/R GR		ALL
TS0096		S283T002-8					WHEEL/04/R GR		ALL
TS0097		S283T002-8					WHEEL/07/R GR		ALL
TS0098		S283T002-8					WHEEL/08/R GR		ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0000

Page 3 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0100		S210T120-38					N 205/149/L004		050-099, 150-156, 162-166, 275-276
TS0100		S210T120-48					N 205/149/L004		157, 167-199, 277-299
TS0101		S210T120-38					N 205/149/R004		150-156, 162-166, 275-276
TS0101		S210T120-48					N 205/149/R004		157, 167-199, 277-299
TS0102		285T0177-1					P036-00/ /		ALL
		1		W0176	A-C			21-58-14	ALL
		2		W0176	A-D			21-58-14	ALL
TS0104		11197-5					0374/170/L083		ALL
TS0120		803127-01					0251/170/R060		ALL
TS0161		102LA2AG					0143/228/		ALL
TS0163		11197-5					0190/178/R041		ALL
TS0164		2156-204A					0386/187/R073		ALL
TS0167		60B50402-16					1570/186/R031		ALL
TS0168		57B50					WS 335/ /		ALL
		RED		W0446	A-A			28-43-11	ALL
		RED		W0446	A-B			28-43-11	ALL
		WHT		W0446	A-E			31-31-25	ALL
		WHT		W0446	A-F			31-31-25	ALL
TS0170		S331T002-10					0144/196/R003		ALL
TS0170		S331T002-4					0144/196/R003		ALL
TS0170		S331T002-1					0144/196/R003		ALL
TS0171		S331T002-10					0144/196/L003		ALL
TS0171		S331T002-4					0144/196/L003		ALL
TS0171		S331T002-1					0144/196/L003		ALL
TS0175		S210T130-19					0253/185/L070		050-099
TS0175		S210T130-19					0268/185/L070		150-156, 162-166, 275-276
TS0175		S210T130-75					0268/185/L070		157, 167-199, 277-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0100

Page 1

Aug 05/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0176		S210T130-21					0195/271/L024		ALL
TS0177		S210T130-19					0661/303/L013		050-099
TS0177		S210T130-19					0654+08/303/L013		150-156, 162-166, 275-276
TS0177		S210T130-75					0654+08/303/L013		157, 167-199, 277-299
TS0178		S210T130-21					0570-640/283/0000		050-099, 150-199, 280-299
TS0178		S210T130-21					0580-640/283/0000		275-278
TS0179		S210T130-19					0709/305/L017		050-099, 162-166
TS0179		S210T130-19					0770/305/R017		150-156, 275-276
TS0179		S210T130-75					0770/305/R017		157, 277-278
TS0179		S210T130-75					0709/305/L017		167-199
TS0179		S210T130-75					0770/305/L017		280-299
TS0180		S210T130-21					1270-335/283/0000		ALL
TS0182		MS28034-1					0580-640/283/0000		050-099, 150-199
TS0182		MS28034-1					0530-640/283/0000		275-278
TS0182		MS28034-1					+560-640/283/0000		280-299
TS0183		MS28034-1					1285-335/283/0000		ALL
TS0184		MS28034-1					0264/185/L070		ALL
TS0185		MS28034-1					0661/303/L013		050-099
TS0185		MS28034-1					0654+08/303/L013		150-199, 275-299
TS0186		MS28034-1					0709/302/L018		050-099
TS0186		MS28034-1					0770/305/L018		150-199, 275-299
TS0187		S242T404-701					P007-00/ /		ALL
		BLK		W1052	A-E			34-22-15	ALL
		BLU		W1052	A-B			34-22-15	ALL
		ORG		W1052	A-C			34-22-15	ALL
		RED		W1052	A-A			34-22-15	ALL
		YEL		W1052	A-D			34-22-15	ALL
TS0188		S242T404-701					P007-00/ /		ALL
		BLK		W1054	A-E			34-22-25	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0100

Page 2

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TS0188</b>		<b>S242T404-701 (continued)</b>					<b>P007-00/ /</b>		<b>ALL</b>
		BLU		W1054	A-B			34-22-25	ALL
		ORG		W1054	A-C			34-22-25	ALL
		RED		W1054	A-A			34-22-25	ALL
		YEL		W1054	A-D			34-22-25	ALL
<b>TS0192</b>		<b>285T0177-3</b>					<b>P036-00/ /</b>		<b>ALL</b>
		1		W0176	A-G			21-25-11	ALL
		2		W0176	A-K			21-25-11	ALL
		3		W0176	A-H			21-25-11	ALL
		4		W0176	A-B			21-25-11	ALL
		5		W0176	A-A			21-25-11	ALL
<b>TS0193</b>		<b>285T0177-3</b>					<b>P037-00/ /</b>		<b>ALL</b>
		1		W0192	A-J			21-25-21	ALL
		2		W0192	A-L			21-25-21	ALL
		3		W0192	A-K			21-25-21	ALL
		4		W0192	A-B			21-25-21	ALL
		5		W0192	A-A			23-25-21	050-099
		5		W0192	A-A			21-25-21	150-199, 275-299
<b>TS0194</b>		<b>S251T362-2</b>					<b>F 089/ /RS</b>		<b>ALL</b>
<b>TS0195</b>		<b>S344T002-7</b>					<b>0990/012/L080</b>		<b>ALL</b>
		GRN		W1300	A-B			28-21-12	ALL
		WHT		W1300	A-C			28-21-12	ALL
		YEL		W1300	A-A			28-21-12	ALL
<b>TS0196</b>		<b>S344T002-7</b>					<b>R/ /RS</b>		<b>ALL</b>
		GRN		W1302	A-B			28-21-12	ALL
		WHT		W1302	A-C			28-21-12	ALL
		YEL		W1302	A-A			28-21-12	ALL
<b>TS0198</b>		<b>624014-1</b>					<b>0859/125/L018</b>		<b>ALL</b>
<b>TS0199</b>		<b>624014-1</b>					<b>0859/125/R059</b>		<b>ALL</b>

TERMINAL STRIP LIST

D280T132

91-21-41

Section TS0100

Page 3 End

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0200		S210T130-19					0768/126/L015		050-099, 150-156, 162-166, 275-276
TS0200		S210T130-75					0768/126/L015		157, 167-199, 277-299
TS0201		S210T130-19					0768/126/R015		050-099, 150-156, 162-166, 275-276
TS0201		S210T130-75					0768/126/R015		157, 167-199, 277-299
TS0202		S283T004-25					//		ALL
TS0203		S283T004-26					//		ALL
TS0204		S283T004-25					//		ALL
TS0205		S283T004-26					//		ALL
TS0207		S283T004-24					NL283/157/0		ALL
TS0208		S283T004-12					//		ALL
TS0209		S283T004-13					//		ALL
TS0210		S283T004-20					//		ALL
TS0211		S283T004-15					//		ALL
TS0212		S283T004-16					//		ALL
TS0214		S283T004-24					NR283/157/0		ALL
TS0215		S283T004-12					//		ALL
TS0216		S283T004-13					//		ALL
TS0217		S283T004-20					//		ALL
TS0218		S283T004-15					//		ALL
TS0219		S283T004-21					//		ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0200

Page 1

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0220		S283T004-21					//		ALL
TS0221		S283T004-18					//		ALL
TS0222		S283T004-19					//		ALL
TS0223		S283T004-17					//		ALL
TS0224		S283T004-22					//		ALL
TS0225		S283T004-23					//		ALL
TS0226		S283T004-17					//		ALL
TS0227		S283T004-20					1198/279/L068		050-099
TS0227		S283T004-20					1198/179/L068		150-199, 275-299
TS0228		S283T004-28					//		ALL
TS0229		S283T004-12					//		ALL
TS0230		285T0177-1					P037-00/ /		ALL
		1		W0192	A-E			21-58-15	ALL
		2		W0192	A-F			21-58-15	ALL
TS0236		975-0304-003					NL201/154/		ALL
		= 1	D1	W0356	400R	18		26-18-12	ALL
		= 1	D1	W0356	453R	18		26-18-12	ALL
		= 2	D1	W0356	454R	18		26-18-12	ALL
TS0237		975-0304-003					NR213/154/		ALL
		= 1	D1	W0356	451R	18		26-18-12	ALL
		= 1	D1	W0356	453R	18		26-18-12	ALL
		= 2	D1	W0356	455R	18		26-18-12	ALL
TS0238		975-0304-003					NL201/154/		ALL
		= 1	D1	W0376	400R	18		26-18-22	ALL
		= 1	D1	W0376	453R	18		26-18-22	ALL
		= 2	D1	W0376	454R	18		26-18-22	ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TS0200

Page 2

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TS0239</b>		<b>975-0304-003</b>					<b>NR213/154/</b>		<b>ALL</b>
		=1	D1	W0376	451R	18		26-18-22	ALL
		=1	D1	W0376	453R	18		26-18-22	ALL
		=2	D1	W0376	455R	18		26-18-22	ALL
<b>TS0240</b>		<b>S283T004-18</b>					<b>//</b>		<b>150-199, 275-299</b>
<b>TS0245</b>		<b>285T0177-1</b>					<b>P037-00/ /</b>		<b>ALL</b>
		1		W0192	A-G			21-26-11	ALL
		2		W0192	A-H			21-26-11	ALL
<b>TS0246</b>		<b>285T0177-1</b>					<b>P036-00/ /</b>		<b>ALL</b>
		1		W0176	A-E			21-26-11	ALL
		2		W0176	A-F			21-26-11	ALL
<b>TS0281</b>		<b>285T0112-6</b>					<b>P001-03/ /</b>		<b>ALL</b>
<b>TS0281</b>		<b>285T0112-4</b>					<b>P001-03/ /</b>		<b>ALL</b>
		A1	1A	W0013	163	24		33-16-11	ALL
		A2	1A	W0013	165	24		33-16-11	ALL
		A3	1A	W0013	164	24		33-16-11	ALL
		B1	1A	W0013	167	24		33-16-11	ALL
		B2	1A	W0013	169	24		33-16-11	ALL
		B3	1A	W0013	168	24		33-16-11	ALL
		DED		W0013	163Z			33-16-11	ALL
		DED		W0013	164Z			33-16-11	ALL
		DED		W0013	165Z			33-16-11	ALL
		G	B	W0013	166	24		33-16-11	ALL
<b>TS0285</b>		<b>11198-4</b>					<b>0845/123/L047</b>		<b>ALL</b>
<b>TS0286</b>		<b>11198-4</b>					<b>0889/123/R064</b>		<b>ALL</b>
<b>TS0289</b>		<b>285T0177-3</b>					<b>P036-00/ /</b>		<b>050-099, 150-199</b>
		1		W0176	A-M			21-24-11	050-099, 150-199
		2		W0176	A-N			21-24-11	050-099, 150-199
		3		W0176	A-P			21-24-11	050-099, 150-199
		4		W0176	A-Q			21-24-11	050-099, 150-199
		5		W0176	A-R			21-24-11	050-099, 150-199
		CAP	Y	W0176	A-R			21-24-11	050-099, 150-199
<b>TS0290</b>		<b>MS28034-1</b>					<b>0883/119/L039</b>		<b>ALL</b>

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0200

Page 3

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0291		MS28034-1					0883/119/R038		ALL
TS0292		MS28034-1					0882/129/L039		ALL
TS0293		MS28034-1					0882/129/R038		ALL
TS0294		MS28034-1					0878/119/L037		ALL
TS0295		MS28034-1					0878/119/R040		ALL
TS0297		MS28034-3					1512/170/R067		050-099, 150-199

**TERMINAL STRIP LIST**

D280T132

**91-21-41**

Section TS0200

Page 4 End

Feb 06/2009



## 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0300		S345T002-128					WING/ /L		ALL
TS0301		S345T002-142					WING/ /L		ALL
TS0302		S345T002-141					WING/ /L		ALL
TS0303		S345T002-140					WING/ /L		ALL
TS0304		S345T002-139					WING/ /L		ALL
TS0305		S345T002-138					WING/ /L		ALL
TS0306		S345T002-137					WING/ /L		ALL
TS0307		S345T002-136					WING/ /L		ALL
TS0308		S345T002-136					WING/ /L		ALL
TS0309		S345T002-135					WING/ /L		ALL
TS0310		S345T002-134					WING/ /L		ALL
TS0311		S345T002-133					WING/ /L		ALL
TS0312		S345T002-132					WING/ /L		ALL
TS0313		S345T002-131					WING/ /L		ALL
TS0314		S345T002-130					WING/ /L		ALL
TS0316		S345T002-146					WING/ /L		ALL
TS0317		S345T002-145					WING/ /L		ALL
TS0318		S345T002-144					WING/ /L		ALL
TS0319		S345T002-143					WING/ /L		ALL
TS0320		S345T002-130					WING/ /L		ALL

### TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0300

Page 1

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0328		S345T002-128					WING/ /R		ALL
TS0329		S345T002-143					WING/ /R		ALL
TS0330		S345T002-144					WING/ /R		ALL
TS0331		S345T002-145					WING/ /R		ALL
TS0332		S345T002-146					WING/ /R		ALL
TS0334		S345T002-128					WING/ /R		ALL
TS0335		S345T002-130					WING/ /R		ALL
TS0336		S345T002-131					WING/ /R		ALL
TS0337		S345T002-132					WING/ /R		ALL
TS0338		S345T002-133					WING/ /R		ALL
TS0339		S345T002-134					WING/ /R		ALL
TS0340		S345T002-135					WING/ /R		ALL
TS0341		S345T002-136					WING/ /R		ALL
TS0342		S345T002-136					WING/ /R		ALL
TS0343		S345T002-137					WING/ /R		ALL
TS0344		S345T002-138					WING/ /R		ALL
TS0345		S345T002-139					WING/ /R		ALL
TS0346		S345T002-140					WING/ /R		ALL
TS0347		S345T002-141					WING/ /R		ALL
TS0348		S345T002-142					WING/ /R		ALL

TERMINAL STRIP LIST

D280T132

91-21-41

Section TS0300

Page 2

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0350		1122413					NL215/145/0000		ALL
TS0351		1122413					NR215/145/0000		ALL
TS0353		253T4015-1					0178/202/L016		ALL
TS0354		253T4015-5					0213/203/L017		ALL
TS0355		253T4015-3					0191/192/L028		ALL
TS0356		1332AH1					0324/197/L043		ALL
TS0372		S210T130-19					0770/305/R012		050-099, 150-156, 162-166, 275-276
TS0372		S210T130-75					0770/305/R012		157, 167-199, 277-299
TS0373		S210T130-21					1040-100/283/0000		050-099
TS0373		S210T130-21					1030/283/0000		150-157
TS0373		S210T130-21					1030/090/0000		162-199
TS0373		S210T130-21					1030-090/283/0000		275-299
TS0375		MS28034-1					1030-090/293/0000		050-099
TS0375		MS28034-1					1030/283/0000		150-157
TS0375		MS28034-1					1030/090/0000		162-199
TS0375		MS28034-1					1030-090/283/0000		275-299
TS0376		MS28034-1					0709/302/R012		050-099
TS0376		MS28034-1					0770/305/R012		150-199, 275-299

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0300

Page 3 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0430		MS28034-1					0882/119/R030		ALL
TS0431		MS28034-1					0882/119/L047		ALL
TS0432		MS28034-1					0870/130/R055		ALL
TS0433		MS28034-1					0871/124/L056		ALL
TS0451		S271T451-1					1043/183/R077		ALL
TS0452		S271T451-1					1041/188/L084		ALL
TS0468		S210T130-19					0568/304/L010		050-099, 150-156, 162-166, 275-276
TS0468		S210T130-75					0568/304/L010		157, 167-199, 277-299
TS0469		S210T130-21					0350-390/283/0000		050-099, 150-199
TS0469		S210T130-21					0400-460/283/0000		275-299
TS0470		S210T130-21					0850-890/305/0000		050-099
TS0470		S210T130-21					0790-850/283/0000		150-157, 275-276
TS0470		S210T130-21					0790-850/305/0000		162-199
TS0470		S210T130-21					0700-890/283/0000		277-299
TS0471		MS28034-1					0568/304/L010		ALL
TS0472		MS28034-1					0770/307/L003		050-099, 150-155, 162-165, 275-276
TS0472		MS28034-1					0767/301/L003		156-157, 166-199, 277-299
TS0473		S271T451-1					1037/188/R084		ALL
TS0474		S271T451-1					1027/188/L084		ALL
TS0476		S210T130-19					0770/307/L003		050-099, 150-155, 162-165, 275-276
TS0476		S210T130-19					0767/300/L003		156, 166, 280-299
TS0476		S210T130-75					0767/300/L003		157, 167-199, 277-278

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0400

Page 1

Feb 06/2009





# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0493		285T0177-1					P037-00/ /		ALL
		1		W1118	A-A			21-26-31	ALL
		2		W1118	A-C			21-26-31	ALL
		CAP	Y	W1118	A-A			21-26-31	050-099, 277-299
TS0494		285T0177-1					P037-00/ /		ALL
		1		W1118	A-E			21-26-31	ALL
		2		W1118	A-F			21-26-31	ALL
TS0495		S210T130-19					0722/156/L073		050-099, 150-156, 162-166, 275-276
TS0495		S210T130-75					0722/156/L073		157, 167-199, 277-299
TS0496		S210T130-21					0620/175/L070		ALL
TS0497		MS28034-3					0620/175/L070		ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0400

Page 2 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS0505		S283U006-7					WHEEL- /01-		050-099, 155-199, 275-299
TS0506		S283U006-7					WHEEL- /02-		050-099, 155-199, 275-299
TS0507		S283U006-7					WHEEL- /03-		050-099, 155-199, 275-299
TS0508		S283U006-7					WHEEL- /04-		050-099, 155-199, 275-299
TS0509		S283U006-7					WHEEL- /05-		050-099, 155-199, 275-299
TS0510		S283U006-7					WHEEL- /06-		050-099, 155-199, 275-299
TS0511		S283U006-7					WHEEL- /07-		050-099, 155-199, 275-299
TS0512		S283U006-7					WHEEL- /08-		050-099, 155-199, 275-299
TS0513		S283T024-3					LNOSE- /09-		050-099, 155-199, 275-299
TS0514		S283T024-3					RNOSE- /10-		050-099, 155-199, 275-299
TS0515		S210T130-21					0279/279/L012		050-099, 162-199
TS0516		10-60498-3					0384/299/L012		050-099, 162-199
TS0517		10-60498-3					1438/293/L026		050-099, 150, 152-199
TS0518		S210T130-21					1419/267/L063		050-099, 150, 152-199
TS0519		10-60498-3					1438/293/R038		050-099, 150, 152-199
TS0520		S210T130-21					1419/267/R063		050-099, 150, 152-199
TS0521		10-60498-3					0444/291/R032		050-099, 162-199
TS0522		S210T130-21					0441/267/R063		050-099, 162-199
TS0523		625704-2					0547/150/L080		050-099, 162-199
		1		W1230		A-B		21-66-11	050-099, 162-199
		2		W1230		B-A		21-66-11	050-099, 162-199

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0500

Page 1

Feb 06/2009



## 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TS0524</b>		<b>285T0177-3</b>					<b>P036-00/ /</b>		<b>050-099, 162-199</b>
		1		W0176	A-I			21-66-11	050-099, 162-199
		2		W0176	A-O			21-66-11	050-099, 162-199
		3		W0176	A-S			21-66-11	050-099, 162-199
		4		W0176	A-T			21-66-11	050-099, 162-199
		5		W0176	A-U			21-66-11	050-099, 162-199
<b>TS0525</b>		<b>285T0177-3</b>					<b>P037-00/ /</b>		<b>050-099, 162-199</b>
		1		W0192	A-I			21-66-21	050-099, 162-199
		2		W0192	A-O			21-66-21	050-099, 162-199
		3		W0192	A-R			21-66-21	050-099, 162-199
		4		W0192	A-P			21-66-21	050-099, 162-199
		5		W0192	A-Q			21-66-21	050-099, 162-199
		CAP	Y	W0192	A-R			21-66-21	050-099, 162-199
<b>TS0526</b>		<b>285T0177-3</b>					<b>P036-00/ /</b>		<b>050-099, 150, 152-199</b>
		1		W0176	B-I			21-66-31	050-099, 150, 152-199
		2		W0176	B-H			21-66-31	050-099, 150, 152-199
		3		W0176	B-N			21-66-31	050-099, 150, 152-199
		4		W0176	B-L			21-66-31	050-099, 150, 152-199
		5		W0176	B-M			21-66-31	050-099, 150, 152-199
<b>TS0527</b>		<b>285T0177-3</b>					<b>P037-00/ /</b>		<b>050-099, 150, 152-199</b>
		1		W0192	A-S			21-66-41	050-099, 150, 152-199
		2		W0192	A-T			21-66-41	050-099, 150, 152-199
		3		W0192	A-W			21-66-41	050-099, 150, 152-199
		4		W0192	A-U			21-66-41	050-099, 150, 152-199
		5		W0192	A-V			21-66-41	050-099, 150, 152-199
		CAP	Y	W0192	A-W			21-66-41	050-099, 150, 152-199

### TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0500

Page 2 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
<b>TS0681</b>		<b>S332T101-22</b>					<b>ENG / /</b>		<b>ALL</b>
		A/1	G3	W3506	452R	16		26-11-11	ALL
		A/1	GW	W3512	451R	16		26-11-11	ALL
		B/2	G3	W3512	452R	16		26-11-11	ALL
		B/2	GW	W3520	452R	16		26-11-11	ALL
<b>TS0682</b>		<b>S332T101-21</b>					<b>ENG / /</b>		<b>ALL</b>
		A/1	GW	W3512	451R	16		26-11-11	ALL
		A/1	G3	W3514	451R	16		26-11-11	ALL
		B/2	G3	W3512	452R	16		26-11-11	ALL
		B/2	GW	W3514	452R	16		26-11-11	ALL
<b>TS0683</b>		<b>S332T101-38</b>					<b>ENG / /</b>		<b>050-099, 162-199, 277-299</b>
		A/1	GW	W3514	451R	16		26-11-11	ALL
		A/1	G3	W3516	452R	16		26-11-11	ALL
		B/2	G3	W3514	452R	16		26-11-11	ALL
		B/2	GW	W3522	452R	16		26-11-11	ALL
<b>TS0684</b>		<b>S332T101-20</b>					<b>ENG / /</b>		<b>ALL</b>
		A/1	GW	W3506	451R	16		26-11-12	ALL
		A/1	G3	W3516	451R	16		26-11-12	ALL
		B/2	G3	W3520	451R	16		26-11-12	ALL
		B/2	GW	W3522	451R	16		26-11-12	ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS0600

Page 1 End

Feb 06/2009



# 767-200/300 WIRING DIAGRAM MANUAL

Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS5072		S231N210-12					0212/195/R080		ALL
TS5081		S251N119-31					0219/202/L021		ALL
TS5082		S251N119-3					0219/202/R021		ALL

## TERMINAL STRIP LIST

D280T132

**91-21-41**

Section TS5000

Page 1 End

Feb 06/2009



Terminal No.	Fix	Part Number Term	Type	Bundle	Wire No.	GA	Station / WL / BL CO	Diagram	Effectivity
TS5132		624014-1					0859/125/L018		ALL
TS5133		625928-2					0879/124/L034		ALL
TS5134		624014-1					0879/125/R059		ALL
TS5135		625928-2					0879/124/R044		ALL

**TERMINAL STRIP LIST**

D280T132

**91-21-41**

Section TS5100

Page 1 End

Feb 06/2009