

**Model : Network Printer Board-F1**  
**Network Multi PDL Printer Board-H1**  
**Network Printer Board-K1**

**Ref. No. : 99-OIPD0-B0038**

**Date : June 1, 1999**

**Approved by :**

*Shinya Kishimoto*

**Location : SYSTEM SOFTWARE**

**Subject : PATCH FILE 52093.PS RELEASE**

**Reason : Job Log Export Support**

Patch files, 52093.ps(File Size=4148 bytes) and 52093.efi(File Size=20492 bytes) were released to support the Job Log Export of Web Spooler in Network Printer Board-F1 v1.0/1.0a and Network Multi PDL Printer Board-H1/K1 v1.0.

**Installation Notes :**

1. For PS and PS/PCL System
  - (1.1) Download the file 52093.ps to the print or direct queue with Fiery Downloader.
  - (1.2) Reboot the server.
  - (1.3) Print the configuration page and check that "52093" is printed out in Update Information on the configuration page.
  - (1.4) Connect to PDL board through a browser
  - (1.5) Select Web Spooler.
  - (1.6) Show the Job Log list on Web Spooler.
  - (1.7) Select File Tab to verify that the "Export Job Log" option is now available.
2. For PCL Only System
  - (2.1) Select "Setup" at Boot up screen.
  - (2.2) Install the Software through the parallel port.
  - (2.3) Download the file 52093.efi with PDL Downloader.
  - (2.4) Exit Setup and reboot.
  - (2.5) Print the configuration page and check that "52093" is printed out in Update Information on the configuration page.
  - (2.6) Connect to PDL board through a browser
  - (2.7) Select Web Spooler.
  - (2.8) Show the Job Log on Web Spooler.
  - (2.8) Select File Tab to verify that the "Export Job Log" option is now available.