



13B2



13B2 -13 Element Wideband Boomer

The 13B2 is as versatile as the 17B2 is specialized. 13B2 will be your choice for high performance across the entire 2 meter band. New and experienced hams will enjoy 15.8 dBi gain on FM, packet, CW, or sideband across the 4 MHz operating range. The 13B2 is easily mounted vertically or horizontally for maximum performance on your favorite mode. Its optimum boom length makes it a popular antenna that fits just about anywhere. The new UltraMatch balanced feed on the 13B2 provides a 50 Ohm match via a standard SO-239 UHF female connector. Model 13B2N has N connector.

17B2 - 17 Element CW/SSB Boomer

The serious two meter operator who is interested in EME, aurora, scatter, SSB, CW, tropo etc, will choose the 17B2. It has 17 elements on a 4.5 wavelength boom. Our computer-aided design supported by precise test range data and the latest manufacturing technology gives you a cleaner pattern and 18 dBi gain in this long boom design. Significant enhancement is provided by the new UltraMatch balanced feed system with N-connector.



The new Cushcraft UltraMatch is a modified T-match system that provides a balanced current distribution on your Boomer. It uses UltraLink teflon dielectric cable allowing for low loss high power applications. UltraMatch is completely enclosed for weather proofing. UltraMatch features an N-connector on the 17B2 and UHF SO239 on the 13B2. When all weather performance is important, you will choose the new UltraMatched Boomers everytime.

17B2



26B2



26B2 - 26 Element Wideband Boomer

This antenna offers the highest gain of any 2 meter FM antenna in the world. The 26B2 includes two complete 13B2 antennas, stacking boom and phasing harnesses.

124WB - 4 Element Wideband Boomer

This is the right choice for packet systems and other applications requiring a dedicated directional antenna.



124WB

A14810S & A1483S2M Yagis

These antennas are the newest computer optimized models of our 2 meter Yagis. We have improved both the pattern and gain to give you better FM coverage.

The A1483S is the low priced quality leader for Packet, FM or even portable use. It is easily rear mounted.

A14810S is one of our best value designs with excellent gain and front-to-back ratio. Use it for long range FM or full band 2 meter operation.

A14810S



A1483S



MODEL	13B2	17B2	124WB	26B2	A1483S	A14810S
Frequency, MHz	144-148	144-145	144-148	144-148	144-148	144-148
No. Elements	13	17	4	26	3	10
Forward Gain, dBi	15.8	18.0	10.2	17	7.8	13.2
Front to Back Ratio, dB	26	26	19	26	18	24
SWR 1.2:1 Typical						
2:1 Bandwidth, MHz	>4	>2	4	>4	>5	34
Power Rating, Watts PEP	1500	1500	1500	1500	1000	1000
3 dB Beamwidth, Degrees						
E Plane	2 x 18	2 x 14.5	60	2x18	66	40
H Plane	2 x 19	2 x 15	88	2x9.5	108	46
Side Lobe Atten., dB, E Plane	>60	>60	40	>60		
Boom Length, ft (m)	15 (4.57)	31 (9.45)	4 (1.22)	15 (4.57)	2.8 (.85)	12 (3.6)
Electrical Wavelength	2.2	4.5	.5	2.2		
Longest Element, in (cm)	39.75 (101)	40.75 (103.5)	40.75 (104)	39.75 (101)	41 (104.1)	40.3 (102.4)
Turning Radius, ft (m)	8.9 (2.7)	17.25 (5.26)	4 (1.22)	10.4 (3.18)	2.8 (.8)	6 (1.8)
Mast Size Range, in (cm)	1.5-2 (3.8-5.1)	1.5-2 (3.8-5.1)	1.25-2 (3.2-5.1)	1.5-2 (3.8-5.1)	1.25-2 (3.2-5.1)	1.25-2 (3.2-5.1)
Wind Load, ft ² (m ²)	1.8 (.17)	3.9 (.36)	.34 (.034)	4.84 (.45)	.27 (.02)	1.21 (.11)
Weight, lb (kg)	6.7 (.31)	15.75 (7.14)	3 (1.36)	21.5 (9.75)	1.5 (.7)	6 (2.7)