



# DECUS

## PROGRAM LIBRARY

DECUS NO.	8-85
TITLE	SET MEMORY EQUAL TO ANYTHING
AUTHOR	Roy S. Taylor
COMPANY	Department of Defense Fort George G. Meade, Maryland
DATE	August 15, 1967
FORMAT	

## SET MEMORY EQUAL TO ANYTHING

DECUS Program Library Write-up

DECUS No. 8-85

This program will preset all locations to any desired settings. Thus, combining a memory clear, set memory equal to HALT, etc. into a single program. The program is loaded via the switch register into core.

### OPERATION

1. Load program below at address shown.
2. Set SR = 0011
3. Depress LOAD ADDRESS.
4. Depress START.
5. After about one second depress LOAD ADDRESS.
6. Set SR = \_\_\_\_\_ (same as setting loaded at address 0015)
7. Raise DEPOSIT key four times.

Memory is now preset to setting you have selected. (Halts, blank, etc.)

### PROGRAM

0010	0015	IR1, 15	/ POINT THAT DATA IS LOADED FIRST VIA INDEX REG
0011	7200	CLA	/ SETS ACCU TO ZERO a bookkeeping function
0012	1015	TAD 15	/ LOAD THE CODE FROM ADDRESS 15 INTO THE AC
0013	3410	DCA I 10	/ DEPOSIT AC VIA IR1 THROUGHOUT CORE
0014	5012	JMP 12	/ REPEAT LOOP
0015	-----	-----	/ load desired coding here.