

K2/100 (Appendix G) MANUAL ERRATA

Rev. H1-4, April 15, 2015

MAKE THESE CHANGES TO YOUR REVISION H1 MANUAL BEFORE YOU BEGIN ASSEMBLY

1. Page 6 (Parts List), Line for Reference Designator “C1, C27”:

Delete “C1” from the Reference Designator column, leaving only “C27”.

Change the QTY from “2” to “1”.

Change the Description to: “Cap. 10-50 pF ceramic trimmer, tan color.”

2. Page 6 (Parts List): Add the following at the bottom of the page:

Picture	Ref. Designator(s)	QTY	Description	Part #
	C1	1	Cap 3-11 pF ceramic trimmer, white color: NOTE: This trimmer is packaged in a separate envelope to help you avoid confusing it with C27. Keep it in its envelope until you are instructed to install it.	E540012

3. Page 16, Right Column: Replace the last two steps with the following. You can cut them out and paste them over the existing steps on the page.

- Install the ceramic trimmer capacitors, C1 and C27. C1 is white and supplied in a separate envelope to help you avoid confusing it with C27. The location for C1 is at the far left near the small notch. C27 installs near the microcontroller, U1 (16F872). C27 is loose in the bag with the other capacitors and is a tan color. Orient the flat side of each trimmer as shown below (Some trimmers are more triangular in shape than shown) :



FLAT SIDE

- Using a small flat-blade screwdriver, set both trimmers to their midpoints (screwdriver slot perpendicular to the flat side as shown above).