

**REVISION LEVEL 22**

DATE: 92-04-06

**Reason:** Tune-up of the board. New printed circuit board version, also prepared for REVISION LEVEL 23 modifications. The board number is located on the wired components side, next to C2525. REVISION LEVEL 23 modifications can be carried out on the REVISION LEVEL 22 version, see below "REVISION LEVEL 23".

**Remarks:** ANALOG BOARD A2 revision level 22 and higher requires software version 3.20 or newer.

ITEM	FROM		TO	
board	4022 245 03656		4022 245 03657	
C2130, C2230	4822 122 33496	100NF	5322 122 34098	10NF
C2136, C2236	-		5322 126 10733	680PF ; added.
C2138, C2238	moved			
C2519	5322 122 32654		removed	
C2539	-		5322 122 32654	22NF ; added over R2540
C2540, C2541	-		5322 122 32654	22NF ; added, from TP511 to common.
C2545	-		5322 122 32654	22NF ; added in series with C2538.
C2704	cancelled, renamed C2707			
C2707	-		5322 122 32654	22NF ; added in series with C2756.
C2756	moved			
R2123, R2223	moved			
R2175, R2275	-		4822 051 55114	511K; added parallel to C2118
R2209	4822 111 91887	42E1	5322 111 91063	34E8
R2300, R2326	-		4822 051 51003	10K ; added between C2320 and C2314
R2340, R2341	4822 051 51001	100E	4822 111 91937	75E
R2342, R2343	4822 111 91885	10E	5322 111 91963	34E8
R2765	-		4822 051 51003	10K; added between R2762 and D2751:2-3.
R2860	moved			
V2112, V2212	4822 130 42513	BC858C	5322 130 42136	BC848C
V2113, V2213	4822 130 42513	BC858C	5322 130 42136	BC848C
V2304	-		5322 130 42136	BC848C; added
V2518	4822 130 42513	BC858C	4822 130 61923	BF821
V2540	-		5322 130 42136	BC848C; added
V2543	4822 130 82262	BAT54S	5322 130 42136	BC848C