

# Digital Multimeter



CE

## FEATURES

- \* 8 Functions AC/DC Voltage, AC/DC Current, Resistance Capacitance, Diode Test and Audible Continuity Beeper
- \* High Voltage 1000V and 20A Current Range
- \* 0.5% Basic DCV Accuracy
- \* LCD Display

## GDM-8034 (3 1/2 Digits)

SPECIFICATIONS	
<b>DC VOLTAGE</b>	
Range	200mV, 2V, 20V, 200V, 1000V 5 ranges
Accuracy	$\pm(0.5\% \text{ rdg} + 1 \text{ digit})$
Input Impedance	10MW
<b>AC VOLTAGE</b>	
Range	200mV, 2V, 20V, 200V, 750V 5 ranges
Accuracy	40Hz ~ 500Hz $\pm(1\% \text{ rdg} + 4 \text{ digits})$
Input Impedance	10M $\Omega$
<b>DC CURRENT</b>	
Range	200 $\mu$ A, 2mA, 20mA, 200mA, 2A, 20A 6 ranges
Accuracy	200 $\mu$ A ~ 200mA $\pm(0.5\% \text{ rdg} + 1 \text{ digit})$ 2A ~ 20A $\pm(1\% \text{ rdg} + 3 \text{ digits})$
<b>AC CURRENT</b>	
Range	200 $\mu$ A, 2mA, 20mA, 200mA, 2A, 20A 6 ranges
Accuracy	40Hz ~ 500Hz on all ranges 200 $\mu$ A ~ 200mA $\pm(1\% \text{ rdg} + 4 \text{ digits})$ 2A ~ 20A $\pm(1.5\% \text{ rdg} + 2 \text{ digits})$
<b>RESISTANCE</b>	
Range	200 $\Omega$ , 2k, 20k, 200k $\Omega$ , 2M $\Omega$ , 20M $\Omega$ 6 ranges
Accuracy	200 $\Omega$ ~ 2M $\Omega$ $\pm(0.75\% \text{ rdg} + 1 \text{ digit})$ 20M $\Omega$ $\pm(1.5\% \text{ rdg} + 5 \text{ digits})$
<b>CAPACITANCE</b>	
Range	2nF, 20nF, 200nF, 2 $\mu$ F, 20 $\mu$ F 5 ranges
Accuracy	$\pm(2\% \text{ rdg} + 4 \text{ digits})$
Test Freq.	300Hz $\pm 5\%$
<b>DIODE TEST</b>	
Test Current	Max. 2.5mA
Open Voltage	Max. 3.2V
<b>CONTINUITY BEEPER</b>	
Description	Buzzer sounds if conductance less than 30 $\Omega$
Test Current	Max. 2.5 mA
Open Voltage	Max. 3.2V
<b>DISPLAY</b>	
0.5" LCD display	
<b>POWER SOURCE</b>	
AC 110V/220V $\pm 15\%$ , 50/60Hz	
<b>ACCESSORIES</b>	
Instruction manual x 1, Power cord x 1, Test lead GTL-107A x 1	
<b>DIMENSIONS &amp; WEIGHT</b>	
245(W) x 95(H) x 280(D) mm, Approx. 2kg	

## ORDERING INFORMATION

**GDM-8034** 3 1/2 Digits LCD Digital Multimeter