

SECULIFE | HIT

TRMS-Medical-Multimeter

3-349-453-03
2/8.09

Features

Digital TRMS handheld multimeter with 23 functions

- Voltage measurement
- Auto-ranging current measurement from 100 μ A (resolution: 10 nA) to 10 A (16 A)
- Capacitance and resistance measurement, diode and continuity testing
- Measuring categories: 1000 V CAT III and 600 V CAT IV
- 1 kHz low-pass filter
- TRMS AC and AC+DC, 20 kHz bandwidth
- Data memory for more than 15,000 measured values

Interface

- Bidirectional infrared interface for communication with the PC (38.4 kBd)
- IR-USB adapter available as option

Power Supply

- Battery operation
- Mains operation via optional broad range variable power pack (95 to 250 V ~)

CAT IV



DKD
Calibration Certificate included

QUALITY MANAGEMENT SYSTEM



DQS Certified per
DIN EN ISO 9001:2000
reg. no. 1262



Applications

The multimeter has been designed especially for use in the field of medical technology, amongst other purposes for servicing, repairing and testing medical devices.

Features

Three Connector Jacks with Automatic Blocking Sockets (ABS) *

All current ranges are implemented via a single connector jack which prevents any possibility of operator error. Beyond this, the automatic blocking sockets prevent incorrect connection of the measurement cables, as well as selection of the wrong measured quantity. Danger to the user, the instrument and the device under test resulting from operator error is thus ruled out.

* Patented (patent no. DE 10 2005 062 624, US 7,439,725)

Overload Protection

The instrument is safeguarded for up to 1000 V in all measuring functions by overload protection. Voltages of greater than 1000 V and current of greater than 10 or 16 A are indicated acoustically. Dangerous contact voltages are indicated when the 1 kHz low-pass filter is activated.

The FUSE display appears in order to indicate that the fuse for the current measuring input has blown.

RMS Value with Distorted Waveshape

The utilized measuring method allows for waveshape independent RMS measurement (TRMS AC and AC+DC) for voltage and current up to 20 kHz.

Activatable Filter for V AC Measurement

A 1 kHz low-pass filter can be activated if required, for example when measuring at electronic frequency converters or switched-mode power supplies.

High Voltage sensor

The input signal is examined for contact danger regardless of the selected input function or filtering.

Measuring 5 V Square-Wave Signals

This function makes it possible to test circuits and transmission cables by measuring the frequency and the keying ratio of pulses with amplitudes of 2 to 5 V and frequencies of 100 Hz to 1 MHz.

Analog Scale for Quick Trend Display – Bar Graph or Pointer

The analog scale (with additional negative range for zero-frequency quantities) allows for faster recognition of measured value fluctuation than is possible with a digital display. The instrument can be switched back and forth between bar graph and pointer display.

Automatic or Manual Measuring Range Selection

Measured quantities are selected by means of a rotary switch and a function key. The measuring range is automatically matched to the measured values. The measuring range can also be selected and fixed manually with a key.

SECULIFE | HIT

TRMS-Medical-Multimeter

Fast Acoustic Continuity Test

Testing for short circuiting and interruption is possible with the selector switch in the \square) position. The threshold value for acoustic signaling can be set to 1, 10, 20, 30, 40 or 90 Ω .

Automatic Storage of Measured Values *

The DATA function automatically saves the digitally displayed measured value after settling in. Acoustic signaling is also used to indicate whether the new measured value deviates from the initial reference value by less or more than 0.1% of the measuring range.

* Patented

Storage of Min-Max Values

Comparable to the slave-pointer function of an analog instrument, the device saves the highest and lowest measured values after the MIN/MAX function has been activated or reset. These extreme values can be queried at the display. The values are acquired using an especially fast sampling rate (40 measurements per second).

Battery Charging Status – Power Saving Circuit

The battery charge level is indicated by means of a 4-segment symbol.

The device is switched off automatically if the measured value remains unchanged for a period of between 10 and 59 minutes (adjustable), and if none of the controls are activated during this time.

Automatic shutdown can be deactivated by switching the instrument to continuous operation.

Protective Cover for Harsh Conditions

The instrument is protected against damage in the event of impacts or dropping by means of a soft rubber cover with tilt stand and test probe holder. The rubber material also assures that the instrument does not wander if it is set up on a vibrating surface.

Infrared Data Interface

The device can be remote configured, and momentary and stored measurement data can be read out via the bidirectional infrared interface. The USB X-TRA interface adapter and **METRAWin 10** software are required to this end (see accessories). Interface protocol and device driver software for LabVIEW[®] (National Instruments[™]) are available upon request.

The infrared interface can be switched off in the standby mode.

DKD Calibration Certificate

The multimeters are furnished with an internationally valid DKD calibration certificate (recognized by EA and ILAC). After the specified calibration interval has elapsed (recommended interval: 1 to 3 years), the multimeters can be inexpensively recalibrated in our own DKD calibration laboratory.

Applicable Regulations and Standards

IEC/EN 61010, part 1:2001/VDE 0411-1:2002	Safety requirements for electrical equipment for measurement, control and laboratory use
DIN EN 61326-1 VDE 0843-20-1	Electrical equipment for measurement, control and laboratory use – EMC requirements – Part 1: General requirements
DIN EN 60529 DIN VDE 0470, part 1	Test instruments and test procedures – degrees of protection provided by enclosures (IP code)

Functions

Voltage V_{AC} TRMS ($R_i \geq 9 M\Omega$)	100 mV / 1 V / 10 V / 100 V / 1000 V
Frequency Hz @ V_{AC}	100 Hz / 1 kHz / 10 kHz / 100 kHz
Voltage Lo ¹⁾ V_{AC} TRMS ($R_i = 1 M\Omega$)	100 mV / 1 V / 10 V / 100 V / 1000 V
Frequency Hz @ Lo ¹⁾ V_{AC}	100 Hz / 1 kHz / 10 kHz / 100 kHz
Low-pass filter	1kHz @ Lo V_{AC} or @ Hz
Voltage V_{DC} ($R_i \geq 9 M\Omega$)	100 mV / 1 V / 10 V / 100 V / 1000 V
Voltage V_{AC+DC} TRMS ($R_i \geq 9 M\Omega$)	100 mV / 1 V / 10 V / 100 V / 1000 V
Bandwidth @ V_{AC+DC} or V_{AC}	20 kHz
Frequency MHz @ 5 V AC \square	100 Hz...1 MHz
Duty cycle %	2,0 % ... 98 %
Resistance Ω	100 Ω / 1 k Ω / 10 k Ω / 100 k Ω / 1 M Ω / 10 M Ω / 40 M Ω
Continuity test \square)	0 ... 100 Ω @ $I_{CONST} = 1$ mA
Diode measurement	0 ... 5,1 V @ $I_{CONST} = 1$ mA
Temperature measurement °C / °F @ T_C	Thermocouple Type K
Temperature measurement °C / °F @ R_{TD}	Pt100 / Pt1000
Capacitance measurement F	10 nF / 100 nF / 1 μ F / 10 μ F / 100 μ F / 1000 μ F
Current A_{DC}	100 μ A / 1 mA / 10 mA / 100 mA / 1 A / 10 A (16 A)
Current A_{AC+DC} TRMS	100 μ A / 1 mA / 10 mA / 100 mA / 1 A / 10 A (16 A)
Current A_{AC} TRMS	100 μ A / 1 mA / 10 mA / 100 mA / 1 A / 10 A (16 A)
Bandwidth @ A_{AC+DC} or A_{AC}	10 kHz
Frequency Hz @ A_{AC}	100 Hz / 1 kHz / 10 kHz / 30 kHz
Data logger function ²⁾ (memory)	4 Mbit = 500 kByte = 15400 measured values
IR-Interface	38400 Bd
Power pack connector socket	✓
Protection ³⁾	IP52
Measurement category	1000 V CAT III and 600 V CAT IV
Calibration	DKD calibration certificate
Protective rubber cover	✓

1) Alternating voltage measurement with specially reduced input impedance

2) Sampling rate adjustable from 0.1 seconds to 9 hours

3) IP65 available with the METRAHIT OUTDOOR model

Included

- 1 multimeter
- 1 pair of safety measurement cables (1.5 m) with 4 mm test probes, 1000 V CAT III, 600 V CAT IV (KS17-2)
- 2 batteries, 1.5 V, type AA
- 1 condensed operating instructions, English/German
- 1 CD ROM, content: operating instructions in English and German)
- 1 DKD calibration certificate
- 1 protective rubber cover light blue
- 1 HC20 hard case

Voluntary Manufacturer's Guarantee

- 24 months for materials and workmanship
- 1 to 3 years for calibration (depending upon application)

Characteristic Values

Meas.-Function	Measuring Range		Resolution at Upper Range Limit		Input Impedance		Intrinsic Uncertainty under Reference Conditions			Overload Capacity ²⁾	
			11999	1199			±(... %rdg. + ... d)	±(... %rdg. + ... d)	±(... %rdg. + ... d)		
V	100 mV	10 μV			≥ 9 MΩ	≥ 9 MΩ // < 50 pF	0.09 + 5 mit ZERO	1 + 30 (> 300 d) ¹⁾	1 + 30 (> 300 d) ¹⁾	1000 V DC AC RMS sine ⁶⁾	continuous
	1 V	100 μV			≥ 9 MΩ	≥ 9 MΩ // < 50 pF	0.05 + 3	0.5 + 9 (> 200 d)	1 + 30 (> 300 d)		
	10 V	1 mV			≥ 9 MΩ	≥ 9 MΩ // < 50 pF	0.05 + 3	0.5 + 9 (> 200 d)	1 + 30 (> 300 d)		
	100 V	10 mV			≥ 9 MΩ	≥ 9 MΩ // < 50 pF	0.05 + 3	0.5 + 9 (> 200 d)	1 + 30 (> 300 d)		
	1000 V	100 mV			≥ 9 MΩ	≥ 9 MΩ // < 50 pF	0.09 + 3	0.5 + 9 (> 200 d)	1 + 30 (> 300 d)		
Voltage drop, approx. at upper range limit							---	~ ¹⁰⁾	≅ ¹⁰⁾		
A	100 μA	10 nA			12 mV	12 mV	0.5 + 5	1.5 + 10 (> 200 d)	1.5 + 30 (> 200 d)	0.2 A	continuous
	1 mA	100 nA			120 mV	120 mV	0.5 + 3	1.5 + 10 (> 200 d)	1.5 + 30 (> 200 d)		
	10 mA	1 μA			16 mV	16 mV	0.5 + 3	1.5 + 10 (> 200 d)	1.5 + 30 (> 200 d)		
	100 mA	10 μA			160 mV	160 mV	0.5 + 3	1.5 + 10 (> 200 d)	1.5 + 30 (> 200 d)		
	1 A	100 μA			40 mV	40 mV	0.9 + 10	1.5 + 10 (> 200 d)	1.5 + 30 (> 200 d)		
	10 A	1 mA			600 mV	600 mV	0.9 + 10	1.5 + 10 (> 200 d)	1.5 + 30 (> 200 d)		
Open-circuit voltage Meas. curr. @ range limit							±(... %rdg. + ... d)				
Ω	100 Ω	10 mΩ			< 1.4 V	Approx. 300 μA	0.2 + 5 with active ZERO function		1000 V DC AC RMS sine	Max. 10 s	
	1 kΩ	100 mΩ			< 1.4 V	Approx. 250 μA	0.2 + 5				
	10 kΩ	1 Ω			< 1.4 V	Approx. 100 μA	0.2 + 5				
	100 kΩ	10 Ω			< 1.4 V	Approx. 12 μA	0.2 + 5				
	1 MΩ	100 Ω			< 1.4 V	Approx. 1.2 μA	0.2 + 5				
	10 MΩ	1 kΩ			< 1.4 V	Approx. 125 nA	0.5 + 10				
	40 MΩ	10 kΩ			< 1.4 V	Approx. 20 nA	2.0 + 10				
⁴⁾	100 Ω	—	0.1 Ω	Approx. 8 V	Approx. 1 mA const.	3 + 5					
→	5.1 V ³⁾	—	1 mV	Approx. 8 V	Approx. 1 mA const.	0.5 + 3					
Discharge resist. U_{0 max}							±(... %rdg. + ... d)				
F	10 nF	10 pF			10 MΩ	0.7 V	1 + 6 ⁴⁾ with active ZERO function		1000 V DC AC RMS sine	Max. 10 s	
	100 nF	100 pF			1 MΩ	0.7 V	1 + 6 ⁴⁾				
	1 μF	1 nF			100 kΩ	0.7 V	1 + 6 ⁴⁾				
	10 μF	10 nF			12 kΩ	0.7 V	1 + 6 ⁴⁾				
	100 μF	100 nF			3 kΩ	0.7 V	5 + 6 ⁴⁾				
	1000 μF	1 μF			3 kΩ	0.7 V	5 + 6 ⁴⁾				
f_{min} ⁵⁾							±(... %rdg. + ... d)				
Hz (V) Hz (A)	100.00 Hz	0.01 Hz				1 Hz	0.05 + 3 ⁸⁾		Hz (V) ⁶⁾ : 1000 V Hz (A): ⁷⁾	Max. 10 s	
	1.0000 kHz	0.1 Hz									
	10.000 kHz	1 Hz									
Hz (V) Hz (A)	100.00 kHz	10 Hz				10 Hz					
	30.00 kHz	10 Hz				10 Hz					
MHz	100 Hz ... 1 MHz	0.01 ... 100 Hz				1 ... 100 Hz	0.05 + 3	> 2 V ... 5 V			
%	2.0 ... 98 %	—	0.01 %	100 Hz ... 1 kHz	1 Hz	1 Hz	0.1 R	> 2 V ... 5 V	1000 V	Max. 10 s	
	5.0 ... 95 %	—	0.01 %	... 10 kHz	1 Hz	1 Hz	0.1 R per kHz	> 2 V ... 5 V			
	10 ... 90 %	—	0.01 %	... 100 kHz	1 Hz	1 Hz	0.1 R per kHz	> 2 V ... 5 V			
°C/°F							±(... %rdg. + ... d)				
°C/°F	Pt100	-200.0 ... +850.0 °C	0.1 °C				0.3 + 15 ⁹⁾		1000 V DC/AC RMS sine	Max. 10 s	
	Pt1000	-150.0 ... +850.0 °C					0.3 + 15 ⁹⁾				
	K (NiCr-Ni)	-250.0 ... +1372.0 °C					1% + 5 K ⁹⁾				

¹⁾ Values of less than 200 digits are suppressed in the mV range.
15 (20) ... 45 ... 65 Hz ... 20 (1) kHz sinusoidal. See influence error on page 4.

²⁾ At 0° ... + 40° C

³⁾ Displays up to max. 5.1 V, "OL" in excess of 5.1 V.

⁴⁾ Applies to measurements at film capacitors

⁵⁾ Lowest measurable frequency for sinusoidal measuring signals symmetrical to the zero point

⁶⁾ Overload capacity of the voltage measurement input:
power limiting: frequency x voltage max. 3 x 10⁹ V x Hz for U > 100 V

⁷⁾ Overload capacity of the current measurement input:
See current measuring ranges for maximum current values.

⁸⁾ Input sensitivity, sinusoidal signal, 10% to 100% of the measuring range

⁹⁾ Plus sensor deviation

¹⁰⁾ Residual value deviates within 1 ... 30 d from the zero point due to TRMS converter when probe tips are short-circuited

¹¹⁾ Off-time > 30 min and T_A ≤ 40 °C

Key: R = measuring range, d= digit(s), rdg. = measured value (reading)

SECULIFE | HIT

TRMS-Medical-Multimeter

Internal Clock

Time format DD.MM.YYYY hh:mm:ss
 Resolution 0.1 s
 Accuracy ±1 min. per month
 Temperature Influence 50 ppm/K

Influencing Quantities and Influence Error

Influencing Quantity	Sphere of Influence	Measured Quantity / Measuring Range ¹⁾	Influence Error (...% rdg. + ... d) / 10 K
Temperature	-10° C ... +21° C and +25° C ... +50° C	V $\overline{\overline{=}}$	0.2 + 10
		V \sim	0.4 + 10
		100 Ω ... 1 M Ω	0.5 + 10
		> 1 M Ω	1 + 10
		mA/A $\overline{\overline{=}}$	0.5 + 10
		mA/A $\overline{\overline{=}}$	0.8 + 10
		10 nF ... 100 μ F	1 + 5
		Hz	0.2 + 10
		°C/°F (Pt100/Pt1000)	0.5 + 10
°C/°F thermocouple K	0.2 + 10		

¹⁾ With zero balancing

Influencing Qty.	Meas. Qty. / Meas. Range	Sphere of Influence	Intrinsic Uncertainty ³⁾ \pm (...% rdg. + ... d)	
Frequency	V _{AC} 100.00 mV ... 100.00 V	> 15 Hz ... 45 Hz	3 + 30	3 + 30
		> 65 Hz ... 1 kHz	2 + 30	3 + 30
		> 1 kHz ... 10 kHz	3 + 30	—
		> 15 Hz ... 45 Hz	2 + 9	3 + 9
		> 65 Hz ... 1 kHz	1 + 9	3 + 9
		> 1 kHz ... 20 kHz	3 + 9	—
	1000.0 V ²⁾	> 15 Hz ... 45 Hz	2 + 9	3 + 9
		> 65 Hz ... 1 kHz	2 + 9	3 + 9
		> 1 kHz ... 10 kHz	3 + 30	—
	A _{AC} 100.00 μ A ... 10.0000 A	> 15 Hz ... 45 Hz	3 + 10	—
		> 65 Hz ... 10 kHz		
	A _{AC} $\overline{\overline{>}}$	100 mV / 1 V / 10 V	> 65 Hz ... 1 kHz	—

²⁾ Power limiting: frequency x voltage max. 3×10^6 V x Hz for U > 100 V

³⁾ The accuracy specification for frequency response is valid within a display value range of 10% to 100% of the measuring range for both measuring modes with the TRMS converter in the AC and (AC+DC) ranges.

Influencing Quantity	Sphere of Influence	Measured Quantity / Measuring Range	Influence Error ⁵⁾
Crest factor CF	1 ... 3	V \sim , A \sim	± 1 % rdg.
	> 3 ... 5		± 3 % rdg.

⁵⁾ Except for sinusoidal waveshape

Influencing Quantity	Sphere of Influence	Measured Quantity	Influence Error
Relative humidity	75%	V, A, Ω , F, Hz, °C	1 x intrinsic uncertainty
	3 days instrument off		
Battery voltage	1.8 to 3.6 V	ditto	Included in intrinsic uncertainty

Influencing Quantity	Sphere of Influence	Measured Quantity / Measuring Range	Damping
Common Mode Interference Voltage	Interference quantity max. 1000 V \sim 50 Hz ... 60 Hz, sine	V $\overline{\overline{=}}$	> 120 dB
		1 V \sim , 10 V \sim	> 80 dB
		100 V \sim 1000 V \sim	> 70 dB > 60 dB
Series Mode Interference Voltage	Interference quantity: V \sim , respective nominal value of the measuring range, max. 1000 V \sim , 50 Hz ... 60 Hz, sine	V $\overline{\overline{=}}$	> 50 dB
		V \sim	> 110 dB

Reference Conditions

Ambient temperature +23 °C ± 2 K
 Relative humidity 40 ... 75%
 Measured qty. frequency 45 ... 65 Hz
 Measured qty. waveshape Sine
 Battery voltage 3 V ± 0.1 V

Response Time (after manual range selection)

Measured Quantity / Measuring Range	Response Time Digital Display	Measured Quantity waveshape
V $\overline{\overline{=}}$, V \sim AV $\overline{\overline{=}}$, A \sim	1.5 s	From 0 to 80% of upper range limit value
100 Ω ... 1 M Ω	2 s	
10/40 M Ω	5 s	
Continuity	< 50 ms	From ∞ to 50% of upper range limit value
°C (Pt 100)	Max. 3 s	
\rightarrow	1.5 s	From 0 to 50% of upper range limit value
10 nF ... 100 μ F	Max. 2 s	
1 000 μ F	Max. 7 s	
> 10 Hz	1.5 s	

Data Interface


Type Optical via infrared light through the housing
 Data transmission Serial, bidirectional (not IrDa compatible)
 Protocol Device specific
 Baud rate 38,400 baud
 Functions – Select/query measuring functions and parameters
 – Query momentary measurement data
 – Read out stored measurement data

The USB X-TRA plug-in interface adapter (see accessories) is used for adaptation to the PC's USB port.

Internal Measured Value Storage

Memory capacity 4 MBit / 540 kB for approx. 15,400 measured values with date and time stamp

Power Supply

Battery	2 ea. 1.5 V mignon cell (2 ea. size AA), alkaline manganese per IEC LR6 (2 ea. 1.2 V NiMH rechargeable battery also possible)
Service life	with alkaline manganese: approx. 200 hours
Battery test	Battery capacity display with battery symbol in 4 segments:  . Querying of momentary battery voltage via menu function.
Power OFF function	Multimeter is switched off automatically: – If battery voltage drops to below prox. 1.8 V – If none of the keys or the rotary switch are activated for an adjustable duration of 10 to 59 minutes, and the multimeter is not in the continuous operation mode
Power pack socket	If the NA X-TRA power pack has been plugged into the instrument, the batteries are disconnected automatically. Rechargeable batteries can only be recharged externally.

Display

LCD panel (65 mm x 36 mm) with analog and digital display including unit of measure, type of current and various special functions

Background illumination

Background illumination is switched off approximately 1 minute after it has been activated.

Analog

Display	LCD scale with bar graph or pointer, depending on the selected parameter setting
Scaling	With 4 division lines each, 1 bar/pointer corresponds to 500 digits at the digital display
Polarity display	With automatic switching
Overflow display	With the ► symbol
Measuring rate	40 measurements per second and display refresh

Digital

Display / char. height	7-segment characters / 15 mm
Number of places	4½ place \cong 11,999 steps
Overflow display	“OL” is displayed for $\geq 12,000$ digits
Polarity display	“–” (minus sign) is displayed if plus pole is connected to “⊥”
Measuring rate	10 and 40 measurements per second with the Min-Max function except for the capacitance, frequency and keying ratio measuring functions
Refresh rate	2 times per sec., every 500 ms

Acoustic Signals

For voltage	Intermittent signal at above 1000 V
For current	Intermittent signal at above 10 A continuous signal at above 16 A

Fuse

Fuse	FF (UR) 10 A/1000 V AC/DC; 10 mm x 38 mm, Switching capacity: 30 kA at 1000 V AC/DC, protects the current measurement input in the 100 μ A through 10 A ranges
------	--

Electrical Safety

Per IEC 61010-1:2001/VDE 0411-1:2002

Safety class	II
Measuring category	III IV
Operating voltage	1000 V 600 V
Fouling factor	2
Test voltage	6.7 kV~

Electromagnetic Compatibility (EMC)

Interference emission	EN 610326-1: 2006, class B
Interference immunity	EN 610326-1: 2006 EN 610326-2-1: 2006

Ambient Conditions

Accuracy range	0 °C ... +40 °C
Operating temp. range	–10° C ... +50° C
Storage temp. range	–25° C ... +70° C (without batteries)
Relative humidity	Max.75%, no condensation allowed
Elevation	To 2000 m
Deployment	Indoors, except within specified ambient conditions

Mechanical Design

Housing	Impact resistant plastic (ABS)
Dimensions	200 x 87 x 45 mm (without protective rubber cover)
Weight	Approx. 0.35 kg with batteries
Protection	Housing: IP 52 (pressure equalization by means of the housing)

Table excerpt regarding significance of the IP code

IP XY (1 st digit X)	Protection against penetration of solid particles	IP XY (2 nd digit Y)	Protection against penetration by water
5	Dust protected	2	Dripping (15° inclination)

SECULIFE | HIT

TRMS-Medical-Multimeter

Accessories for Operation at a PC

Interface Adapter for USB Connection

The USB X-TRA bidirectional interface adapter includes the following functions:

- Configure the **SECULIFE HIT** from a PC.
- Transmit live measurement data to the PC.
- Read out data from memory at the **SECULIFE HIT**.

The adapter does not require a separate power supply. Its baud rate is 38,400 baud. A CD ROM is included which contains current drivers for Windows operating systems.



METRAwin[®]10/METRAHit[®] Software

METRAwin[®]10/METRAHit[®] PC software is a multilingual, measurement data logging program for recording, visualizing and documenting measured values from **SECULIFE HIT** multimeters.

Communication between the PC and the measuring instrument(s) is established via available interfaces and memory adapters. Telephone modems can be interconnected as well.

Depending upon device type, one or several of the following operating modes are possible:


- **Device Configuration**
Remote configuration and querying of device-specific functions and parameters, for example measuring function, measuring range and memory parameters. Frequently used device settings can be saved to configuration files for easy recall.
- **Online Recording of Measurement Data**
Read-in, display and recording of momentarily measured data from the interconnected device.
 - Number of measuring channels up to 10
 - Start recording manual, triggered by measured value, time triggered
 - Recording mode
 - > time controlled with sampling interval of 0.05 s* ... 1 s ... 60 min
 - > manually controlled
 - > measured value controlled in event of exceeded limit/delta value
 - Recording duration max. 10 million intervals

* Depending upon device type, measuring function, number of measuring channels and communication (e.g. via modem), sample intervals of less than 1 s cannot be used.


- **Reading Out and Visualizing Stored Data**
If supported by the device: read-in and display of offline data recorded to device memory.

For purposes of analysis, data recorded online or read in from the device's memory can be displayed in various formats:

Y(t)-recorder display for up to 6 channels



XY-recorder display for up to 4 channels



Multimeter-display for up to 4 channels



Tabular display for up to 10 channels

System Requirements

METRAwin 10 (as from version 5.3) can be run on IBM compatible PCs with Microsoft Windows[®] 98, ME, NT 4.0, 2000, XP or VISTA.

SECULIFE | HIT

TRMS-Medical-Multimeter

Order Information

Designation	Type	Article Number
4½-place (12,000 digits) TRMS multimeter with direct, alternating and pulsating voltage measurement (TRMS values), frequency measurement, resistance measurement, continuity test, diode measurement and temperature measurement with type K thermocouples LCD with 15 mm characters, analog bar graph and background illumination Measuring categories: 600 V/CAT IV, 1000 V/CAT III		
All multimeters include the KS17-2 measurement cable set, two mignon batteries, condensed operating instructions, CD ROM, DKD calibration certificate Additional direct, alternating and pulsating current measurement (TRMS values), additional broad range capacitance measurement, precision temperature measurement with Pt100 or Pt1000 platinum resistance thermometers, frequency and keying ratio measurement, with power pack socket and IR interface, 4 MB data memory, protective rubber cover		
	SECULIFE HIT	M687A
Accessories for operation at a PC		
IR-USB bidirectional interface adapter	USB X-TRA	Z216C
METRAwin10 software	METRAwin10	GTZ3240000R0001
Accessories for temp. measurement with resistance thermometer		
Pt100 temperature sensor for surface and immersion measurement, -40 to +600° C	Z3409	GTZ3409000R0001
Pt1000 temperature sensor for measurement in gases and liquids, -50 to +220° C	TF220	Z102A
Pt100 oven sensor, -50 to +550° C	TF550	GTZ3408000R0001
Ten adhesive Pt100 temperature sensors, -50 to +550° C	TS Chipset	GTZ3406000R0001
Replacement fuse		
Fuses (pack of 10)	FF (UR) 10 A / 1000 V AC/DC	Z109L
Power pack	NA X-TRA	Z218G
Protective rubber cover and carrying strap	GH X-TRA	Z104C

Transport Accessories

HitBag Cordura Belt Pouch

For multimeters (with/without protective rubber cover)



HC20 Hard Case

For multimeter (with/without protective rubber cover) and accessories



F836 Ever-Ready Case

For multimeter (without protective rubber cover) and accessories



F829 Carrying Pouch

For multimeters (with/without protective rubber cover) and accessories



Designation	Type	Article Number
Imitation leather carrying pouch	F829	GTZ3301000R0003
Cordura belt pouch	HitBag	Z115A
Imitation leather ever-ready case with cable compartment	F836	GTZ3302000R0001
Ever-ready case for 2 SECULIFE HIT, 2 adapters and accessories	F840	GTZ3302001R0001
Hard case for one SECULIFE HIT and accessories	HC20	Z113A
Hard case for two SECULIFE HIT and accessories	HC30	Z113A

For additional information regarding accessories please refer to:

- our Measuring Instruments and Testers catalog.
- our website www.gossenmetrawatt.com

SECULIFE | HIT

TRMS-Medical-Multimeter

Current Measuring Accessories								
All current sensors and transformers are equipped with a connector cable (1.2 to 1.5 m long) with 4 mm safety banana plugs								
Type	Designation	Measuring Range	Meas. Category	Max. Wire Dia.	Transformation Factor	Frequency Range	Intrinsic Uncertainty ±(% rdg. + ...)	Article Number
DC/AC Current Sensors with Voltage Output								
Z201A	DC/AC clip-on current sensor, with battery mode (30 h)	0.01 ... 20 A~/30 A-	300 V / CAT III	19 mm	100 mV/A	<u>DC ... 400 Hz</u> ... 20 kHz	1% + 0.002 A	Z201A
Z202A	DC/AC clip-on current sensor, with 2 measuring ranges, battery mode (50 h)	0.1 ... 20 A~/30 A-; 1 ... 200 A~/300 A-	300 V / CAT III	19 mm	10 mV/A, 1 mV/A	<u>DC ... 2 kHz</u> ... 10 kHz	1% + 0.03 A, 1% + 0.3 A	Z202A
Z203A	DC/AC clip-on current sensor, with 2 measuring ranges, battery mode (50 h)	1 ... 200 A~/300 A-; 1 ... 1000 A~/A-	300 V / CAT III	31 mm	1 mV/A	DC ... 10 kHz	1% + 0.5 A	Z203A
Z13B	DC/AC clip-on current sensor, with 2 measuring ranges, battery mode (50 h)	0.2 ... 40 A~/60 A-; 0.5 ... 400 A~/600A-	300 V / CAT IV	50 mm	10 mV/A, 1 mV/A	<u>DC ... 65 Hz</u> ... 10 kHz	1.5% + 0.5 A 2.5%	Z13B
AC Current Sensors with Voltage Output								
WZ12B	AC clip-on current sensor	10 mA~ ... 100 A~	300 V / CAT III	15 mm	100 mV/A	<u>45 ... 65</u> ... 500 Hz	1.5% + 0.1 mA	Z219B
WZ12C	AC clip-on current sensor, with 2 measuring ranges	1 mA~ ... 15 A~, 1 ... 150 A~	300 V / CAT III	15 mm	1 mV/mA, 1 mV/A	<u>45 ... 65</u> ... 400 Hz	3% + 0.15 mA, 2% + 0.1 A	Z219C
WZ11B	AC clip-on current sensor, with 2 measuring ranges	0.5 ... 20 A~, 5 ... 200 A~	600 V / CAT III	20 mm	100 mV/A, 10 mV/A	<u>30...48...65</u> ... 500 Hz	1 ... 3%	Z208B
Z3512A	AC clip-on current sensor, with 4 measuring ranges	1 mA ... 1/10/100/ 1000 A~	600 V / CAT III	52 mm	1 V/A, 100 mV/A, 10 mV/A, 1 mV/A	<u>10...48...65</u> ... 3 kHz	0.5 ... 3%, 0.2 ... 1%	Z225A
AF033A	AmpFLEX flexible AC current sensor with 2 measuring ranges, battery (150 h)	5 ... 30 A~, 5 ... 300 A~	1000 V / CAT III	Length: 600 mm	100 mV/A, 10 mV/A	<u>10 ... 100 Hz</u> ... 20 kHz	1% + 0.5 A, 1% + 0.5 A	Z207A
AF11A	AmpFLEX flexible AC current sensor, battery (150 h)	5 ... 1000 A~	1000 V / CAT III	Length: 450 mm	1 mV/A	<u>10 ... 100 Hz</u> ... 20 kHz	1% + 2 A	Z207D
AF33A	AmpFLEX flexible AC current sensor with 2 measuring ranges, battery (150 h)	5 ... 300 A~, 5 ... 3000 A~	1000 V / CAT III	Length: 900 mm	10 mV/A, 1 mV/A	<u>10 ... 100 Hz</u> ... 20 kHz	1% + 0.5 A, 1% + 2 A	Z207B
AF101A	AmpFLEX flexible AC current sensor with 2 measuring ranges, battery (150 h)	5 A~... 1 k A~, 50 A~... 10 k A~	1000 V / CAT III	Length: 1200 mm	1 mV/A, 0.1 mV/A	<u>10 ... 100 Hz</u> ... 20 kHz	1% + 2 A, 1% + 10 A	Z207C
AC Current Transformer with Current Output								
WZ12A	AC clip-on current transformer	15 ... 180 A~	300 V / CAT III	15 mm	1 mA/A	<u>45 ... 65</u> ... 400 Hz	3%	Z219A
WZ12D	AC clip-on current transformer	30 mA ... 150 A~	300 V / CAT III	15 mm	1 mA/A	<u>45 ... 65</u> ... 500 Hz	2.5% + 0.1 mA	Z219D
WZ11A	AC clip-on current transformer	1 ... 200 A~	600 V / CAT III	20 mm	1 mA/A	<u>48 ... 65</u> ... 400 Hz	1 ... 3%	Z208A
Z3511	AC clip-on current transformer	4 ... 500 A~	600 V / CAT III	30 x 63 mm	1 mA/A	<u>48 ... 65</u> ... 1 kHz	3% + 0.4 A	GTZ 3511 000 R0001
Z3512	AC clip-on current transformer	0.5 ... 1000 A~	600 V / CAT III	52 mm	1 mA/A	<u>30...48...65</u> ... 5 kHz	0.5% ... 0.7%	GTZ 3512 000 R0001
Z3514	AC clip-on current transformer	1 ... 2000 A ~	600 V / CAT III	64 x 150 mm	1 mA/A	<u>30...48...65</u> ... 5 kHz	0.5% + 0.1 A	GTZ 3514 000 R0001
Shunt Resistors for Multimeters without Current Measuring Function								
NW300mA	Plug-in shunt resistor, encapsulated	0 ... 300 mA	300 V / CAT III	—	1 mV/mA	DC ... 10 kHz	0.5%	Z205C
NW3A	Plug-in shunt resistor, encapsulated	0 ... 3 A	300 V / CAT III	—	100 mV/A	DC ... 10 kHz	0.5%	Z205B

● with adjustable transformation factor 1: 1 / 10 / 100 / 1000

◆ without adjustable transformation factor

Prepared in Germany • Subject to change without notice • PDF version available on the Internet