

# Keysight N6700 Low-Profile Modular Power System (MPS)

Small, flexible and fast power supplies for ATE applications



## Key features

- 50 W, 100 W, 300 W and 500 W DC power modules
- 3 mainframes: 400 W, 600 W, 1200 W
- True 1-rack unit height (1U)
- Mix-and-match over 30 DC power modules of 3 different performance levels: Basic, hi-performance, and precision
- Stable, reliable DC outputs up to 150 V and up to 50 A
- USB, LAN (LXI Core) and GPIB standard
- Simultaneous voltage and current measurements with N6760 series
- List mode software sequencer (arb mode)
- Built-in digitizer (scope mode) <sup>1</sup>
- Over-voltage, current and temperature protection
- Multiple-output front panel display and controls
- Virtual channels for easy parallel up to 100 A

1. All modules except N6760 series require Option 054.

1. N6700B Low-profile MPS, 300 W
2. N6701A Low-profile MPS, 600 W
3. N6702A Low-profile MPS, 1200 W
4. Bright LCD display, view status indicators and settings for all 4 outputs
5. System keys for easy access to front panel menus and settings
6. Navigation keys
7. Output keys
8. Numeric entry keys

	Mainframe	Basic modules	High performance	Precision modules
	<b>N6700B, N6701A, N6702A</b>	<b>N673X, N674X, N677X</b>	<b>N675X</b>	<b>N676X</b>
Power	300 W, 600 W, 1200 W	50 W, 100 W, 300 W	50 W, 100 W, 300 W, 500 W	50 W, 100 W, 300 W, 500 W
Voltage	Up to 350 V (with multiple modules in series)	Up to 150 V	Up to 60 V	Up to 60 V
Current	Up to 100 A (with two 50A modules in parallel)	Up to 20A	Up to 50A	Up to 50 A
Voltmeter accuracy	N/A	0.1% + 20 mV	0.05% + 10 mV	0.016% + 1.5 mV
Ammeter accuracy	N/A	0.15% + 2 mA	0.1% + 4 mA	0.05% + 100 nA
Arbitrary waveform <sup>1</sup> generator function	Create waveforms up to 512 points			
Scope function <sup>1</sup>	Digitizes at up to 100 kHz, up to 512 k points, up to 16-bits (module dependent)			
Interface	GPIB, USB, LAN (LXI Core)			

1. Code must be written by the user. Examples available online.

## Options and accessories

Option	Option description
N6709A	Special rack mount kit
N6708A	Filler module kit

Example applications	Using built-in features
PC motherboard power on/off	Output sequencing for proper turn on/off
Sleep-mode current for RF power amps	µA current measurement capabilities
Military/police radio	High-power (up to 500 W) with low-level (mA) measurement accuracy
Base station power amps	High-power (up to 500 W) with low-level (mA) measurement accuracy
Automotive “crank” test	Built-in arbitrary waveform generator

For R&D applications, consider the N6705B DC Power Analyzer.



### Three-Year Warranty

[www.keysight.com/find/ThreeYearWarranty](http://www.keysight.com/find/ThreeYearWarranty)

Keysight's commitment to superior product quality and lower total cost of ownership. The only test and measurement company with three-year warranty standard on all instruments, worldwide.



### Keysight Assurance Plans

[www.keysight.com/find/AssurancePlans](http://www.keysight.com/find/AssurancePlans)

Up to five years of protection and no budgetary surprises to ensure your instruments are operating to specification so you can rely on accurate measurements.

